

91-21-11

WIRE LIST



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-----------------|-----------|-------------|-------------|------|-------------|-------------|------|-------------|
| EFFECTIVE PAGES | | | W0010 cont. | | | W0010 cont. | | |
| | 1 thru 31 | Aug 05/2009 | | 26 | May 20/2005 | | 53 | May 20/2005 |
| | 32 | BLANK | | 27 | May 20/2005 | | 54 | May 20/2005 |
| W0010 | 1 | May 20/2005 | | 28 | May 20/2005 | | 55 | May 20/2005 |
| | 2 | May 20/2005 | | 29 | May 20/2005 | W0020 | 1 | Jan 21/2005 |
| | 3 | May 20/2005 | | 30 | May 20/2005 | | 2 | Jan 21/2005 |
| | 4 | May 20/2005 | | 31 | May 20/2005 | | 3 | Jan 21/2005 |
| | 5 | May 20/2005 | | 32 | May 20/2005 | | 4 | Jan 21/2005 |
| | 6 | May 20/2005 | | 33 | May 20/2005 | | 5 | Jan 21/2005 |
| | 7 | May 20/2005 | | 34 | May 20/2005 | | 6 | Jan 21/2005 |
| | 8 | May 20/2005 | | 35 | May 20/2005 | | 7 | Jan 21/2005 |
| | 9 | May 20/2005 | | 36 | May 20/2005 | | 8 | Jan 21/2005 |
| | 10 | May 20/2005 | | 37 | May 20/2005 | | 9 | Jan 21/2005 |
| | 11 | May 20/2005 | | 38 | May 20/2005 | | 10 | Jan 21/2005 |
| | 12 | May 20/2005 | | 39 | May 20/2005 | | 11 | Jan 21/2005 |
| | 13 | May 20/2005 | | 40 | May 20/2005 | | 12 | Jan 21/2005 |
| | 14 | May 20/2005 | | 41 | May 20/2005 | | 13 | Jan 21/2005 |
| | 15 | May 20/2005 | | 42 | May 20/2005 | | 14 | Jan 21/2005 |
| | 16 | May 20/2005 | | 43 | May 20/2005 | | 15 | Jan 21/2005 |
| | 17 | May 20/2005 | | 44 | May 20/2005 | | 16 | Jan 21/2005 |
| | 18 | May 20/2005 | | 45 | May 20/2005 | | 17 | Jan 21/2005 |
| | 19 | May 20/2005 | | 46 | May 20/2005 | | 18 | Jan 21/2005 |
| | 20 | May 20/2005 | | 47 | May 20/2005 | | 19 | Jan 21/2005 |
| | 21 | May 20/2005 | | 48 | May 20/2005 | | 20 | Jan 21/2005 |
| | 22 | May 20/2005 | | 49 | Jun 06/2008 | | 21 | Jan 21/2005 |
| | 23 | May 20/2005 | | 50 | Jun 06/2008 | | 22 | Jan 21/2005 |
| | 24 | May 20/2005 | | 51 | May 20/2005 | | 23 | Jan 21/2005 |
| | 25 | May 20/2005 | | 52 | May 20/2005 | | 24 | Jan 21/2005 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280T132

EFFECTIVE PAGES

Page 1
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0020 cont. | | | W0030 cont. | | | W0040 cont. | | |
| | 25 | Jan 21/2005 | | 25 | May 20/2005 | | 17 | Mar 14/2007 |
| | 26 | Jan 21/2005 | | 26 | May 20/2005 | | 18 | Mar 14/2007 |
| | 27 | Jan 21/2005 | | 27 | May 20/2005 | | 19 | Mar 14/2007 |
| W0030 | 1 | Jan 21/2005 | | 28 | May 20/2005 | | 20 | Mar 14/2007 |
| | 2 | Jan 21/2005 | | 29 | May 20/2005 | | 21 | Mar 14/2007 |
| | 3 | Jan 21/2005 | | 30 | May 20/2005 | | 22 | Mar 14/2007 |
| | 4 | Jan 21/2005 | | 31 | May 20/2005 | | 23 | Mar 14/2007 |
| | 5 | Jan 21/2005 | | 32 | May 20/2005 | | 24 | Mar 14/2007 |
| | 6 | Jan 21/2005 | | 33 | May 20/2005 | | 25 | Mar 14/2007 |
| | 7 | Jan 21/2005 | | 34 | May 20/2005 | | 26 | Mar 14/2007 |
| | 8 | Jan 21/2005 | | 35 | May 20/2005 | | 27 | Mar 14/2007 |
| | 9 | Jan 21/2005 | W0040 | 1 | Jan 21/2005 | | 28 | Mar 14/2007 |
| | 10 | Jan 21/2005 | | 2 | Jan 21/2005 | | 29 | Mar 14/2007 |
| | 11 | Jan 21/2005 | | 3 | Jan 21/2005 | | 30 | Mar 14/2007 |
| | 12 | Jan 21/2005 | | 4 | Jan 21/2005 | | 31 | Mar 14/2007 |
| | 13 | Jan 21/2005 | | 5 | Mar 14/2007 | | 32 | Mar 14/2007 |
| | 14 | Jan 21/2005 | | 6 | Mar 14/2007 | | 33 | Mar 14/2007 |
| | 15 | May 20/2005 | | 7 | Mar 14/2007 | | 34 | Mar 14/2007 |
| | 16 | May 20/2005 | | 8 | Mar 14/2007 | | 35 | Mar 14/2007 |
| | 17 | May 20/2005 | | 9 | Mar 14/2007 | | 36 | Mar 14/2007 |
| | 18 | May 20/2005 | | 10 | Mar 14/2007 | | 37 | Mar 14/2007 |
| | 19 | May 20/2005 | | 11 | Mar 14/2007 | | 38 | Mar 14/2007 |
| | 20 | May 20/2005 | | 12 | Mar 14/2007 | | 39 | Mar 14/2007 |
| | 21 | May 20/2005 | | 13 | Mar 14/2007 | | 40 | Mar 14/2007 |
| | 22 | May 20/2005 | | 14 | Mar 14/2007 | | 41 | Mar 14/2007 |
| | 23 | May 20/2005 | | 15 | Mar 14/2007 | | 42 | Mar 14/2007 |
| | 24 | May 20/2005 | | 16 | Mar 14/2007 | | 43 | Mar 14/2007 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES

Page 2
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0040 cont. | | | W0060 cont. | | | W0060 cont. | | |
| | 44 | Mar 14/2007 | | 4 | Jan 21/2005 | | 31 | Jan 21/2005 |
| | 45 | Mar 14/2007 | | 5 | Jan 21/2005 | | 32 | Jan 21/2005 |
| | 46 | Mar 14/2007 | | 6 | Jan 21/2005 | | 33 | Jan 21/2005 |
| | 47 | Mar 14/2007 | | 7 | Jan 21/2005 | | 34 | Jan 21/2005 |
| | 48 | Mar 14/2007 | | 8 | Jan 21/2005 | | 35 | Jan 21/2005 |
| | 49 | Mar 14/2007 | | 9 | Jan 21/2005 | | 36 | Jan 21/2005 |
| | 50 | Mar 14/2007 | | 10 | Jan 21/2005 | | 37 | Jan 21/2005 |
| | 51 | Mar 14/2007 | | 11 | Jan 21/2005 | | 38 | Jan 21/2005 |
| | 52 | Mar 14/2007 | | 12 | Jan 21/2005 | | 39 | Jan 21/2005 |
| W0050 | 1 | Jan 21/2005 | | 13 | Jan 21/2005 | | 40 | Jan 21/2005 |
| | 2 | Jan 21/2005 | | 14 | Jan 21/2005 | | 41 | Jan 21/2005 |
| | 3 | Jan 21/2005 | | 15 | Jan 21/2005 | | 42 | Jan 21/2005 |
| | 4 | May 20/2005 | | 16 | Jan 21/2005 | | 43 | Jan 21/2005 |
| | 5 | May 20/2005 | | 17 | Jan 21/2005 | | 44 | Jan 21/2005 |
| | 6 | May 20/2005 | | 18 | Jan 21/2005 | | 45 | Jan 21/2005 |
| | 7 | May 20/2005 | | 19 | Jan 21/2005 | | 46 | Jan 21/2005 |
| | 8 | May 20/2005 | | 20 | Jan 21/2005 | | 47 | Jan 21/2005 |
| | 9 | Mar 14/2007 | | 21 | Jan 21/2005 | | 48 | Jan 21/2005 |
| | 10 | Mar 14/2007 | | 22 | Jan 21/2005 | | 49 | Jan 21/2005 |
| | 11 | Mar 14/2007 | | 23 | Jan 21/2005 | | 50 | Jan 21/2005 |
| | 12 | Mar 14/2007 | | 24 | Jan 21/2005 | | 51 | Jan 21/2005 |
| | 13 | Mar 14/2007 | | 25 | Jan 21/2005 | | 52 | Jan 21/2005 |
| | 14 | Mar 14/2007 | | 26 | Jan 21/2005 | | 53 | Jan 21/2005 |
| | 15 | Mar 14/2007 | | 27 | Jan 21/2005 | | 54 | Jan 21/2005 |
| W0060 | 1 | Jan 21/2005 | | 28 | Jan 21/2005 | | 55 | Jan 21/2005 |
| | 2 | Jan 21/2005 | | 29 | Jan 21/2005 | | 56 | Jan 21/2005 |
| | 3 | Jan 21/2005 | | 30 | Jan 21/2005 | | 57 | Jan 21/2005 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 3
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0060 cont. | | | W0060 cont. | | | W0070 cont. | | |
| | 58 | Jan 21/2005 | | 85 | Jan 21/2005 | | 12 | Jan 21/2005 |
| | 59 | Jan 21/2005 | | 86 | Jan 21/2005 | | 13 | Jan 21/2005 |
| | 60 | Jan 21/2005 | | 87 | Jan 21/2005 | | 14 | Jan 21/2005 |
| | 61 | Jan 21/2005 | | 88 | Jan 21/2005 | | 15 | Jan 21/2005 |
| | 62 | Jan 21/2005 | | 89 | Jan 21/2005 | | 16 | Jan 21/2005 |
| | 63 | Jan 21/2005 | | 90 | Jan 21/2005 | | 17 | Jan 21/2005 |
| | 64 | Jan 21/2005 | | 91 | Jan 21/2005 | | 18 | Jan 21/2005 |
| | 65 | Jan 21/2005 | | 92 | Jan 21/2005 | | 19 | Jan 21/2005 |
| | 66 | Jan 21/2005 | | 93 | Jan 21/2005 | W0080 | 1 | Jan 21/2005 |
| | 67 | Jan 21/2005 | | 94 | Jan 21/2005 | | 2 | Jan 21/2005 |
| | 68 | Jan 21/2005 | | 95 | Jan 21/2005 | | 3 | Jan 21/2005 |
| | 69 | Jan 21/2005 | | 96 | Jan 21/2005 | | 4 | Jan 21/2005 |
| | 70 | Jan 21/2005 | | 97 | Jan 21/2005 | | 5 | Jan 21/2005 |
| | 71 | Jan 21/2005 | | 98 | Jan 21/2005 | | 6 | Jan 21/2005 |
| | 72 | Jan 21/2005 | | 99 | Jan 21/2005 | | 7 | Jan 21/2005 |
| | 73 | Jan 21/2005 | | 100 | Jan 21/2005 | | 8 | Jan 21/2005 |
| | 74 | Jan 21/2005 | W0070 | 1 | Jan 21/2005 | | 9 | Jan 21/2005 |
| | 75 | Jan 21/2005 | | 2 | Jan 21/2005 | | 10 | Jan 21/2005 |
| | 76 | Jan 21/2005 | | 3 | Jan 21/2005 | | 11 | Jan 21/2005 |
| | 77 | Jan 21/2005 | | 4 | Jan 21/2005 | | 12 | Jan 21/2005 |
| | 78 | Jan 21/2005 | | 5 | Jan 21/2005 | | 13 | Jan 21/2005 |
| | 79 | Jan 21/2005 | | 6 | Jan 21/2005 | | 14 | Jan 21/2005 |
| | 80 | Jan 21/2005 | | 7 | Jan 21/2005 | | 15 | Jan 21/2005 |
| | 81 | Jan 21/2005 | | 8 | Jan 21/2005 | | 16 | Jan 21/2005 |
| | 82 | Jan 21/2005 | | 9 | Jan 21/2005 | W0090 | 1 | Jan 21/2005 |
| | 83 | Jan 21/2005 | | 10 | Jan 21/2005 | | 2 | Jan 21/2005 |
| | 84 | Jan 21/2005 | | 11 | Jan 21/2005 | | 3 | Jan 21/2005 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 4
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0090 cont. | | | W0100 cont. | | | W0100 cont. | | |
| | 4 | Jan 21/2005 | | 13 | May 20/2005 | | 40 | Mar 14/2007 |
| | 5 | Jan 21/2005 | | 14 | May 20/2005 | | 41 | Mar 14/2007 |
| | 6 | Jan 21/2005 | | 15 | May 20/2005 | | 42 | Sep 04/2008 |
| | 7 | Jan 21/2005 | | 16 | May 20/2005 | | 43 | Mar 14/2007 |
| | 8 | Jan 21/2005 | | 17 | May 20/2005 | | 44 | Mar 14/2007 |
| | 9 | Jan 21/2005 | | 18 | May 20/2005 | | 45 | Mar 14/2007 |
| | 10 | Jan 21/2005 | | 19 | May 20/2005 | | 46 | Mar 14/2007 |
| | 11 | Jan 21/2005 | | 20 | May 20/2005 | | 47 | Mar 14/2007 |
| | 12 | Jan 21/2005 | | 21 | May 20/2005 | | 48 | Mar 14/2007 |
| | 13 | Jan 21/2005 | | 22 | May 20/2005 | | 49 | Mar 14/2007 |
| | 14 | Jan 21/2005 | | 23 | May 20/2005 | | 50 | Mar 14/2007 |
| | 15 | Mar 14/2007 | | 24 | May 20/2005 | | 51 | Mar 14/2007 |
| | 16 | Mar 14/2007 | | 25 | May 20/2005 | | 52 | Mar 14/2007 |
| | 17 | Mar 14/2007 | | 26 | May 20/2005 | | 53 | Mar 14/2007 |
| | 18 | Mar 14/2007 | | 27 | May 20/2005 | | 54 | Mar 14/2007 |
| W0100 | 1 | Jan 21/2005 | | 28 | May 20/2005 | W0110 | 1 | Jan 21/2005 |
| | 2 | Jan 21/2005 | | 29 | May 20/2005 | | 2 | Jan 21/2005 |
| | 3 | Jan 21/2005 | | 30 | Aug 15/2007 | | 3 | Jan 21/2005 |
| | 4 | Jan 21/2005 | | 31 | Aug 15/2007 | | 4 | Jan 21/2005 |
| | 5 | Jan 21/2005 | | 32 | May 20/2005 | | 5 | Jan 21/2005 |
| | 6 | Jan 21/2005 | | 33 | May 20/2005 | | 6 | Jan 21/2005 |
| | 7 | Jan 21/2005 | | 34 | May 20/2005 | | 7 | Jan 21/2005 |
| | 8 | Jan 21/2005 | | 35 | Mar 14/2007 | | 8 | Jan 21/2005 |
| | 9 | Jan 21/2005 | | 36 | Mar 14/2007 | | 9 | Jan 21/2005 |
| | 10 | Jan 21/2005 | | 37 | Mar 14/2007 | | 10 | May 20/2005 |
| | 11 | Jan 21/2005 | | 38 | Mar 14/2007 | | 11 | May 20/2005 |
| | 12 | May 20/2005 | | 39 | Mar 14/2007 | | 12 | May 20/2005 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 5
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0110 cont. | | | W0120 cont. | | | W0130 cont. | | |
| | 13 | May 20/2005 | | 8 | Jan 21/2005 | | 13 | Aug 15/2007 |
| | 14 | May 20/2005 | | 9 | Jan 21/2005 | | 14 | Aug 15/2007 |
| | 15 | May 20/2005 | | 10 | Jan 21/2005 | | 15 | Aug 15/2007 |
| | 16 | May 20/2005 | | 11 | Jan 21/2005 | | 16 | Aug 15/2007 |
| | 17 | May 20/2005 | | 12 | Jan 21/2005 | | 17 | Aug 15/2007 |
| | 18 | May 20/2005 | | 13 | Jan 21/2005 | | 18 | Aug 15/2007 |
| | 19 | May 20/2005 | | 14 | Jan 21/2005 | | 19 | Jan 21/2005 |
| | 20 | May 20/2005 | | 15 | Jan 21/2005 | | 20 | Jan 21/2005 |
| | 21 | May 20/2005 | | 16 | Jan 21/2005 | | 21 | Jan 21/2005 |
| | 22 | May 20/2005 | | 17 | Jan 21/2005 | | 22 | Jan 21/2005 |
| | 23 | May 20/2005 | | 18 | Jan 21/2005 | | 23 | Jan 21/2005 |
| | 24 | May 20/2005 | | 19 | Jan 21/2005 | | 24 | Jan 21/2005 |
| | 25 | May 20/2005 | | 20 | Jan 21/2005 | | 25 | Jan 21/2005 |
| | 26 | May 20/2005 | | 21 | Jan 21/2005 | | 26 | Jan 21/2005 |
| | 27 | May 20/2005 | | 22 | Jan 21/2005 | | 27 | Jan 21/2005 |
| | 28 | May 20/2005 | W0130 | 1 | Jan 21/2005 | | 28 | Jan 21/2005 |
| | 29 | May 20/2005 | | 2 | Jan 21/2005 | | 29 | Jan 21/2005 |
| | 30 | May 20/2005 | | 3 | Jan 21/2005 | | 30 | Jan 21/2005 |
| | 31 | Mar 14/2007 | | 4 | Jan 21/2005 | | 31 | Jan 21/2005 |
| | 32 | Mar 14/2007 | | 5 | Jan 21/2005 | | 32 | Jan 21/2005 |
| W0120 | 1 | Jan 21/2005 | | 6 | Jan 21/2005 | | 33 | Jan 21/2005 |
| | 2 | Jan 21/2005 | | 7 | Jan 21/2005 | | 34 | Jan 21/2005 |
| | 3 | Jan 21/2005 | | 8 | Jan 21/2005 | | 35 | Jan 21/2005 |
| | 4 | Jan 21/2005 | | 9 | Aug 15/2007 | | 36 | Jan 21/2005 |
| | 5 | Jan 21/2005 | | 10 | Aug 15/2007 | | 37 | Jan 21/2005 |
| | 6 | Jan 21/2005 | | 11 | Aug 15/2007 | | 38 | Jan 21/2005 |
| | 7 | Jan 21/2005 | | 12 | Aug 15/2007 | | 39 | Jan 21/2005 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 6
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0130 cont. | | | W0130 cont. | | | W0130 cont. | | |
| | 40 | Jan 21/2005 | | 67 | Mar 14/2007 | | 94 | Mar 14/2007 |
| | 41 | Jan 21/2005 | | 68 | Mar 14/2007 | | 95 | Mar 14/2007 |
| | 42 | Mar 14/2007 | | 69 | Mar 14/2007 | | 96 | Mar 14/2007 |
| | 43 | Mar 14/2007 | | 70 | Mar 14/2007 | | 97 | Mar 14/2007 |
| | 44 | Mar 14/2007 | | 71 | Mar 14/2007 | | 98 | Mar 14/2007 |
| | 45 | Mar 14/2007 | | 72 | Mar 14/2007 | | 99 | Mar 14/2007 |
| | 46 | Mar 14/2007 | | 73 | Mar 14/2007 | | 100 | Mar 14/2007 |
| | 47 | Mar 14/2007 | | 74 | Mar 14/2007 | | 101 | Mar 14/2007 |
| | 48 | Mar 14/2007 | | 75 | Mar 14/2007 | | 102 | Mar 14/2007 |
| | 49 | Mar 14/2007 | | 76 | Mar 14/2007 | | 103 | Mar 14/2007 |
| | 50 | Mar 14/2007 | | 77 | Mar 14/2007 | | 104 | Mar 14/2007 |
| | 51 | Mar 14/2007 | | 78 | Mar 14/2007 | | 105 | Mar 14/2007 |
| | 52 | Mar 14/2007 | | 79 | Mar 14/2007 | | 106 | Mar 14/2007 |
| | 53 | Mar 14/2007 | | 80 | Mar 14/2007 | | 107 | Mar 14/2007 |
| | 54 | Mar 14/2007 | | 81 | Mar 14/2007 | | 108 | Mar 14/2007 |
| | 55 | Mar 14/2007 | | 82 | Mar 14/2007 | | 109 | Mar 14/2007 |
| | 56 | Mar 14/2007 | | 83 | Mar 14/2007 | | 110 | Mar 14/2007 |
| | 57 | Mar 14/2007 | | 84 | Mar 14/2007 | | 111 | Mar 14/2007 |
| | 58 | Mar 14/2007 | | 85 | Mar 14/2007 | W0140 | 1 | Mar 14/2007 |
| | 59 | Mar 14/2007 | | 86 | Mar 14/2007 | | 2 | Mar 14/2007 |
| | 60 | Mar 14/2007 | | 87 | Mar 14/2007 | | 3 | Mar 14/2007 |
| | 61 | Mar 14/2007 | | 88 | Mar 14/2007 | | 4 | Mar 14/2007 |
| | 62 | Mar 14/2007 | | 89 | Mar 14/2007 | | 5 | Mar 14/2007 |
| | 63 | Mar 14/2007 | | 90 | Mar 14/2007 | | 6 | Mar 14/2007 |
| | 64 | Mar 14/2007 | | 91 | Mar 14/2007 | | 7 | Mar 14/2007 |
| | 65 | Mar 14/2007 | | 92 | Mar 14/2007 | | 8 | Mar 14/2007 |
| | 66 | Mar 14/2007 | | 93 | Mar 14/2007 | | 9 | Mar 14/2007 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280T132

EFFECTIVE PAGES

Page 7
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0140 cont. | | | W0140 cont. | | | W0140 cont. | | |
| | 10 | Mar 14/2007 | | 37 | Mar 14/2007 | | 64 | Aug 15/2007 |
| | 11 | Mar 14/2007 | | 38 | Mar 14/2007 | | 65 | Aug 15/2007 |
| | 12 | Mar 14/2007 | | 39 | Mar 14/2007 | | 66 | Aug 15/2007 |
| | 13 | Mar 14/2007 | | 40 | Mar 14/2007 | | 67 | Aug 15/2007 |
| | 14 | Mar 14/2007 | | 41 | Mar 14/2007 | | 68 | Aug 15/2007 |
| | 15 | Mar 14/2007 | | 42 | Mar 14/2007 | | 69 | Mar 14/2007 |
| | 16 | Mar 14/2007 | | 43 | Mar 14/2007 | | 70 | Mar 14/2007 |
| | 17 | Mar 14/2007 | | 44 | Mar 14/2007 | | 71 | Mar 14/2007 |
| | 18 | Mar 14/2007 | | 45 | Mar 14/2007 | | 72 | Mar 14/2007 |
| | 19 | Mar 14/2007 | | 46 | Mar 14/2007 | | 73 | Mar 14/2007 |
| | 20 | Mar 14/2007 | | 47 | Mar 14/2007 | | 74 | Mar 14/2007 |
| | 21 | Mar 14/2007 | | 48 | Mar 14/2007 | | 75 | Mar 14/2007 |
| | 22 | Mar 14/2007 | | 49 | Mar 14/2007 | | 76 | Mar 14/2007 |
| | 23 | Mar 14/2007 | | 50 | Mar 14/2007 | | 77 | Mar 14/2007 |
| | 24 | Mar 14/2007 | | 51 | Mar 14/2007 | | 78 | Mar 14/2007 |
| | 25 | Mar 14/2007 | | 52 | Mar 14/2007 | | 79 | Mar 14/2007 |
| | 26 | Mar 14/2007 | | 53 | Mar 14/2007 | | 80 | Mar 14/2007 |
| | 27 | Mar 14/2007 | | 54 | Mar 14/2007 | | 81 | Mar 14/2007 |
| | 28 | Mar 14/2007 | | 55 | Mar 14/2007 | | 82 | Mar 14/2007 |
| | 29 | Mar 14/2007 | | 56 | Mar 14/2007 | | 83 | Mar 14/2007 |
| | 30 | Mar 14/2007 | | 57 | Mar 14/2007 | | 84 | Mar 14/2007 |
| | 31 | Mar 14/2007 | | 58 | Mar 14/2007 | | 85 | Mar 14/2007 |
| | 32 | Mar 14/2007 | | 59 | Mar 14/2007 | | 86 | Mar 14/2007 |
| | 33 | Mar 14/2007 | | 60 | Mar 14/2007 | | 87 | Mar 14/2007 |
| | 34 | Mar 14/2007 | | 61 | Mar 14/2007 | | 88 | Mar 14/2007 |
| | 35 | Mar 14/2007 | | 62 | Aug 15/2007 | | 89 | Mar 14/2007 |
| | 36 | Mar 14/2007 | | 63 | Aug 15/2007 | | 90 | Mar 14/2007 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 8
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0140 cont. | | | W0150 cont. | | | W0170 cont. | | |
| R | 91 | Mar 14/2007 | | 2 | Mar 14/2007 | | 2 | Mar 14/2007 |
| | 92 | Aug 05/2009 | | 3 | Mar 14/2007 | | 3 | Mar 14/2007 |
| | 93 | Mar 14/2007 | | 4 | Mar 14/2007 | | 4 | Mar 14/2007 |
| | 94 | Mar 14/2007 | | 5 | Mar 14/2007 | | 5 | Mar 14/2007 |
| | 95 | Mar 14/2007 | | 6 | Mar 14/2007 | | 6 | Mar 14/2007 |
| | 96 | Mar 14/2007 | | 7 | Mar 14/2007 | | 7 | Mar 14/2007 |
| | 97 | Mar 14/2007 | | 8 | Mar 14/2007 | | 8 | Mar 14/2007 |
| | 98 | Mar 14/2007 | | 9 | Mar 14/2007 | | 9 | Mar 14/2007 |
| | 99 | Feb 06/2009 | | 10 | Mar 14/2007 | | 10 | Feb 06/2009 |
| | 100 | Feb 06/2009 | | 11 | Mar 14/2007 | | 11 | Feb 06/2009 |
| | 101 | Feb 06/2009 | | 12 | Mar 14/2007 | | 12 | Feb 06/2009 |
| | 102 | Feb 06/2009 | | 13 | Mar 14/2007 | | 13 | Feb 06/2009 |
| | 103 | Feb 06/2009 | | 14 | Mar 14/2007 | | 14 | Feb 06/2009 |
| | 104 | Feb 06/2009 | | 15 | Mar 14/2007 | | 15 | Feb 06/2009 |
| | 105 | Feb 06/2009 | | 16 | Mar 14/2007 | | 16 | Feb 06/2009 |
| | 106 | Feb 06/2009 | | 17 | Mar 14/2007 | | 17 | Feb 06/2009 |
| | 107 | Feb 06/2009 | | 18 | Mar 14/2007 | | 18 | Feb 06/2009 |
| | 108 | Feb 06/2009 | W0160 | 1 | Mar 14/2007 | | 19 | Feb 06/2009 |
| | 109 | Feb 06/2009 | | 2 | Mar 14/2007 | | 20 | Feb 06/2009 |
| | 110 | Feb 06/2009 | | 3 | Mar 14/2007 | | 21 | Feb 06/2009 |
| | 111 | Feb 06/2009 | | 4 | Mar 14/2007 | | 22 | Feb 06/2009 |
| | 112 | Feb 06/2009 | | 5 | Mar 14/2007 | | 23 | Feb 06/2009 |
| | 113 | Feb 06/2009 | | 6 | Mar 14/2007 | | 24 | Feb 06/2009 |
| | 114 | Feb 06/2009 | | 7 | Mar 14/2007 | | 25 | Feb 06/2009 |
| | 115 | Feb 06/2009 | | 8 | Mar 14/2007 | | 26 | Feb 06/2009 |
| | 116 | Feb 06/2009 | | 9 | Mar 14/2007 | | 27 | Feb 06/2009 |
| W0150 | 1 | Mar 14/2007 | W0170 | 1 | Mar 14/2007 | | 28 | Feb 06/2009 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280T132

EFFECTIVE PAGES

Page 9
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0170 cont. | | | W0170 cont. | | | W0180 cont. | | |
| | 29 | Feb 06/2009 | | 56 | Feb 06/2009 | | 17 | Feb 06/2009 |
| | 30 | Feb 06/2009 | | 57 | Feb 06/2009 | | 18 | Feb 06/2009 |
| | 31 | Feb 06/2009 | | 58 | Feb 06/2009 | | 19 | Feb 06/2009 |
| | 32 | Mar 14/2007 | | 59 | Feb 06/2009 | | 20 | Feb 06/2009 |
| | 33 | Mar 14/2007 | | 60 | Feb 06/2009 | | 21 | Feb 06/2009 |
| | 34 | Mar 14/2007 | | 61 | Feb 06/2009 | | 22 | Feb 06/2009 |
| | 35 | Mar 14/2007 | | 62 | Feb 06/2009 | R | 23 | Aug 05/2009 |
| | 36 | Mar 14/2007 | | 63 | Feb 06/2009 | | 24 | Feb 06/2009 |
| | 37 | Mar 14/2007 | | 64 | Feb 06/2009 | | 25 | Feb 06/2009 |
| | 38 | Mar 14/2007 | | 65 | Feb 06/2009 | | 26 | Feb 06/2009 |
| R | 39 | Aug 05/2009 | | 66 | Feb 06/2009 | | 27 | Feb 06/2009 |
| | 40 | Feb 06/2009 | W0180 | 1 | Mar 14/2007 | | 28 | Feb 06/2009 |
| | 41 | Mar 14/2007 | | 2 | Mar 14/2007 | | 29 | Feb 06/2009 |
| | 42 | Mar 14/2007 | | 3 | Mar 14/2007 | | 30 | Feb 06/2009 |
| | 43 | Mar 14/2007 | | 4 | Mar 14/2007 | | 31 | Feb 06/2009 |
| | 44 | Mar 14/2007 | | 5 | Mar 14/2007 | W0190 | 1 | Feb 06/2009 |
| | 45 | Mar 14/2007 | | 6 | Mar 14/2007 | | 2 | Feb 06/2009 |
| | 46 | Mar 14/2007 | | 7 | Mar 14/2007 | | 3 | Feb 06/2009 |
| R | 47 | Aug 05/2009 | | 8 | Mar 14/2007 | | 4 | Feb 06/2009 |
| | 48 | Mar 14/2007 | | 9 | Mar 14/2007 | | 5 | Feb 06/2009 |
| | 49 | Mar 14/2007 | | 10 | Mar 14/2007 | | 6 | Feb 06/2009 |
| | 50 | Mar 14/2007 | | 11 | Mar 14/2007 | | 7 | Feb 06/2009 |
| | 51 | Jun 06/2008 | | 12 | Mar 14/2007 | | 8 | Feb 06/2009 |
| | 52 | Jun 06/2008 | | 13 | Feb 06/2009 | | 9 | Feb 06/2009 |
| | 53 | Feb 06/2009 | | 14 | Feb 06/2009 | | 10 | Feb 06/2009 |
| | 54 | Feb 06/2009 | | 15 | Feb 06/2009 | | 11 | Feb 06/2009 |
| | 55 | Feb 06/2009 | | 16 | Feb 06/2009 | | 12 | Feb 06/2009 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 10
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0190 cont. | | | W0190 cont. | | | W0200 cont. | | |
| | 13 | Feb 06/2009 | | 40 | Feb 06/2009 | | 4 | Mar 14/2007 |
| | 14 | Feb 06/2009 | | 41 | Feb 06/2009 | | 5 | Mar 14/2007 |
| | 15 | Feb 06/2009 | | 42 | Feb 06/2009 | | 6 | Mar 14/2007 |
| | 16 | Feb 06/2009 | | 43 | Feb 06/2009 | | 7 | Mar 14/2007 |
| | 17 | Feb 06/2009 | | 44 | Feb 06/2009 | W0210 | 1 | Mar 14/2007 |
| | 18 | Feb 06/2009 | | 45 | Feb 06/2009 | | 2 | Mar 14/2007 |
| | 19 | Feb 06/2009 | | 46 | Feb 06/2009 | | 3 | Mar 14/2007 |
| | 20 | Feb 06/2009 | | 47 | Feb 06/2009 | | 4 | Jun 06/2008 |
| | 21 | Feb 06/2009 | | 48 | Mar 14/2007 | | 5 | Jun 06/2008 |
| | 22 | Feb 06/2009 | | 49 | Mar 14/2007 | | 6 | Jun 06/2008 |
| | 23 | Feb 06/2009 | | 50 | Mar 14/2007 | | 7 | Jun 06/2008 |
| | 24 | Feb 06/2009 | | 51 | Mar 14/2007 | | 8 | Jun 06/2008 |
| | 25 | Feb 06/2009 | | 52 | Mar 14/2007 | | 9 | Mar 14/2007 |
| | 26 | Feb 06/2009 | | 53 | Mar 14/2007 | | 10 | Mar 14/2007 |
| | 27 | Feb 06/2009 | | 54 | Mar 14/2007 | W0220 | 1 | Mar 14/2007 |
| | 28 | Feb 06/2009 | | 55 | Feb 06/2009 | | 2 | Mar 14/2007 |
| | 29 | Feb 06/2009 | | 56 | Feb 06/2009 | | 3 | Mar 14/2007 |
| | 30 | Feb 06/2009 | | 57 | Feb 06/2009 | | 4 | Jun 06/2008 |
| | 31 | Feb 06/2009 | | 58 | Feb 06/2009 | | 5 | Mar 14/2007 |
| | 32 | Feb 06/2009 | | 59 | Feb 06/2009 | | 6 | Mar 14/2007 |
| | 33 | Feb 06/2009 | | 60 | Feb 06/2009 | | 7 | Mar 14/2007 |
| | 34 | Feb 06/2009 | | 61 | Feb 06/2009 | | 8 | Mar 14/2007 |
| | 35 | Feb 06/2009 | | 62 | Feb 06/2009 | W0230 | 1 | Aug 15/2007 |
| | 36 | Feb 06/2009 | | 63 | Feb 06/2009 | | 2 | Aug 15/2007 |
| | 37 | Feb 06/2009 | W0200 | 1 | Mar 14/2007 | W0240 | 1 | Mar 14/2007 |
| | 38 | Feb 06/2009 | | 2 | Mar 14/2007 | | 2 | Mar 14/2007 |
| | 39 | Feb 06/2009 | | 3 | Mar 14/2007 | | 3 | Mar 14/2007 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 11
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|---------|------|-------------|-------------|------|-------------|
| W0240 cont. | | | W0310 | 1 | Mar 14/2007 | W0380 cont. | | |
| | 4 | Mar 14/2007 | W0320 | 1 | Mar 14/2007 | | 4 | Mar 14/2007 |
| | 5 | Mar 14/2007 | W0330 | 1 | Mar 14/2007 | | 5 | Mar 14/2007 |
| | 6 | Mar 14/2007 | W0340 | 1 | Mar 14/2007 | W0390 | 1 | Mar 14/2007 |
| | 7 | Mar 14/2007 | | 2 | Mar 14/2007 | | 2 | Mar 14/2007 |
| | 8 | Mar 14/2007 | W0350 | 1 | Mar 14/2007 | | 3 | Mar 14/2007 |
| | 9 | Mar 14/2007 | | 2 | Mar 14/2007 | | 4 | Mar 14/2007 |
| | 10 | Mar 14/2007 | | 3 | Mar 14/2007 | | 5 | Mar 14/2007 |
| W0250 | 1 | Mar 14/2007 | | 4 | Mar 14/2007 | | 6 | Mar 14/2007 |
| | 2 | Mar 14/2007 | | 5 | Mar 14/2007 | | 7 | Mar 14/2007 |
| W0260 | 1 | Mar 14/2007 | | 6 | Mar 14/2007 | | 8 | Mar 14/2007 |
| | 2 | Mar 14/2007 | | 7 | Mar 14/2007 | | 9 | Mar 14/2007 |
| | 3 | Feb 06/2009 | | 8 | Mar 14/2007 | | 10 | Mar 14/2007 |
| | 4 | Feb 06/2009 | W0360 | 1 | Mar 14/2007 | | 11 | Mar 14/2007 |
| | 5 | Feb 06/2009 | W0370 | 1 | Mar 14/2007 | | 12 | Mar 14/2007 |
| | 6 | Feb 06/2009 | | 2 | Mar 14/2007 | W0400 | 1 | Mar 14/2007 |
| | 7 | Mar 14/2007 | | 3 | Mar 14/2007 | | 2 | Mar 14/2007 |
| W0270 | 1 | Mar 14/2007 | | 4 | Mar 14/2007 | | 3 | Mar 14/2007 |
| | 2 | Mar 14/2007 | | 5 | Mar 14/2007 | | 4 | Mar 14/2007 |
| | 3 | Mar 14/2007 | | 6 | Mar 14/2007 | | 5 | Mar 14/2007 |
| W0280 | 1 | Mar 14/2007 | | 7 | Mar 14/2007 | | 6 | Mar 14/2007 |
| | 2 | Mar 14/2007 | | 8 | Mar 14/2007 | | 7 | Mar 14/2007 |
| | 3 | Mar 14/2007 | | 9 | Mar 14/2007 | | 8 | Mar 14/2007 |
| | 4 | Mar 14/2007 | | 10 | Mar 14/2007 | | 9 | Mar 14/2007 |
| W0290 | 1 | Mar 14/2007 | | 11 | Mar 14/2007 | | 10 | Mar 14/2007 |
| | 2 | Mar 14/2007 | W0380 | 1 | Mar 14/2007 | | 11 | Mar 14/2007 |
| W0300 | 1 | Mar 14/2007 | | 2 | Mar 14/2007 | | 12 | Mar 14/2007 |
| | 2 | Mar 14/2007 | | 3 | Mar 14/2007 | | 13 | Mar 14/2007 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES

Page 12
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0400 cont. | | | W0440 cont. | | | W0470 cont. | | |
| | 14 | Mar 14/2007 | | 11 | Mar 07/2008 | | 4 | Mar 14/2007 |
| | 15 | Mar 14/2007 | | 12 | Mar 07/2008 | | 5 | Mar 14/2007 |
| W0410 | 1 | Mar 14/2007 | W0450 | 1 | Mar 14/2007 | | 6 | Mar 14/2007 |
| | 2 | Mar 14/2007 | | 2 | Mar 14/2007 | | 7 | Mar 14/2007 |
| | 3 | Mar 14/2007 | | 3 | Mar 14/2007 | | 8 | Mar 14/2007 |
| | 4 | Mar 14/2007 | | 4 | Mar 14/2007 | | 9 | Mar 14/2007 |
| | 5 | Mar 14/2007 | | 5 | Mar 14/2007 | | 10 | Mar 14/2007 |
| | 6 | Mar 14/2007 | | 6 | Mar 14/2007 | | 11 | Mar 14/2007 |
| | 7 | Mar 14/2007 | | 7 | Mar 14/2007 | | 12 | Mar 14/2007 |
| | 8 | Mar 14/2007 | | 8 | Mar 14/2007 | | 13 | Mar 14/2007 |
| W0420 | 1 | Mar 14/2007 | | 9 | Mar 14/2007 | W0480 | 1 | Mar 14/2007 |
| | 2 | Mar 14/2007 | | 10 | Mar 14/2007 | | 2 | Mar 14/2007 |
| | 3 | Mar 14/2007 | | 11 | Mar 14/2007 | | 3 | Mar 14/2007 |
| | 4 | Mar 14/2007 | | 12 | Mar 14/2007 | | 4 | Mar 14/2007 |
| W0430 | 1 | Mar 14/2007 | | 13 | Mar 14/2007 | | 5 | Mar 14/2007 |
| | 2 | Mar 14/2007 | | 14 | Mar 14/2007 | | 6 | Mar 14/2007 |
| | 3 | Mar 14/2007 | W0460 | 1 | Mar 14/2007 | | 7 | Mar 14/2007 |
| W0440 | 1 | Mar 14/2007 | | 2 | Mar 14/2007 | | 8 | Mar 14/2007 |
| | 2 | Mar 14/2007 | | 3 | Mar 14/2007 | | 9 | Mar 14/2007 |
| | 3 | Mar 14/2007 | | 4 | Mar 14/2007 | W0490 | 1 | Mar 14/2007 |
| | 4 | Mar 14/2007 | | 5 | Mar 14/2007 | | 2 | Mar 14/2007 |
| | 5 | Mar 14/2007 | | 6 | Mar 14/2007 | | 3 | Mar 14/2007 |
| | 6 | Mar 14/2007 | | 7 | Mar 14/2007 | | 4 | Mar 14/2007 |
| | 7 | Mar 14/2007 | | 8 | Mar 14/2007 | | 5 | Mar 14/2007 |
| | 8 | Mar 14/2007 | W0470 | 1 | Mar 14/2007 | W0500 | 1 | Mar 14/2007 |
| | 9 | Mar 07/2008 | | 2 | Mar 14/2007 | | 2 | Mar 14/2007 |
| | 10 | Mar 07/2008 | | 3 | Mar 14/2007 | | 3 | Mar 14/2007 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280T132

EFFECTIVE PAGES

Page 13
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0500 cont. | | | W0510 cont. | | | W0580 cont. | | |
| | 4 | Mar 14/2007 | | 12 | Mar 14/2007 | | 3 | Mar 14/2007 |
| | 5 | Mar 14/2007 | | 13 | Mar 14/2007 | | 4 | Mar 14/2007 |
| | 6 | Mar 14/2007 | | 14 | Mar 14/2007 | | 5 | Mar 14/2007 |
| | 7 | Mar 14/2007 | | 15 | Mar 14/2007 | | 6 | Mar 14/2007 |
| | 8 | Mar 14/2007 | W0520 | 1 | Mar 14/2007 | | 7 | Mar 14/2007 |
| | 9 | Mar 14/2007 | | 2 | Mar 14/2007 | | 8 | Mar 14/2007 |
| | 10 | Mar 14/2007 | | 3 | Mar 14/2007 | | 9 | Mar 14/2007 |
| | 11 | Mar 14/2007 | | 4 | Mar 14/2007 | | 10 | Mar 14/2007 |
| | 12 | Mar 14/2007 | W0530 | 1 | Mar 14/2007 | | 11 | Mar 14/2007 |
| | 13 | Mar 14/2007 | W0540 | 1 | Mar 14/2007 | | 12 | Mar 14/2007 |
| | 14 | Mar 14/2007 | W0570 | 1 | Mar 14/2007 | | 13 | Mar 14/2007 |
| | 15 | Mar 14/2007 | | 2 | Mar 14/2007 | | 14 | Mar 14/2007 |
| | 16 | Mar 14/2007 | | 3 | Mar 14/2007 | W0590 | 1 | Feb 06/2009 |
| | 17 | Mar 14/2007 | | 4 | Mar 14/2007 | | 2 | Feb 06/2009 |
| | 18 | Mar 14/2007 | | 5 | Mar 14/2007 | | 3 | Feb 06/2009 |
| | 19 | Mar 14/2007 | | 6 | Mar 14/2007 | | 4 | Feb 06/2009 |
| W0510 | 1 | Mar 14/2007 | | 7 | Mar 14/2007 | | 5 | Feb 06/2009 |
| | 2 | Mar 14/2007 | | 8 | Mar 14/2007 | | 6 | Feb 06/2009 |
| | 3 | Mar 14/2007 | | 9 | Mar 14/2007 | | 7 | Feb 06/2009 |
| | 4 | Mar 14/2007 | | 10 | Mar 14/2007 | | 8 | Feb 06/2009 |
| | 5 | Mar 14/2007 | | 11 | Mar 14/2007 | | 9 | Feb 06/2009 |
| | 6 | Mar 14/2007 | | 12 | Mar 14/2007 | | 10 | Feb 06/2009 |
| | 7 | Mar 14/2007 | | 13 | Mar 14/2007 | | 11 | Feb 06/2009 |
| | 8 | Mar 14/2007 | | 14 | Mar 14/2007 | | 12 | Feb 06/2009 |
| | 9 | Mar 14/2007 | R | 15 | Aug 05/2009 | | 13 | Feb 06/2009 |
| | 10 | Mar 14/2007 | W0580 | 1 | Mar 14/2007 | | 14 | Feb 06/2009 |
| | 11 | Mar 14/2007 | | 2 | Mar 14/2007 | | 15 | Feb 06/2009 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 14
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0590 cont. | | | W0610 cont. | | | W0620 cont. | | |
| | 16 | Feb 06/2009 | | 3 | Mar 14/2007 | | 16 | Mar 14/2007 |
| | 17 | Feb 06/2009 | | 4 | Mar 14/2007 | | 17 | Mar 14/2007 |
| W0600 | 1 | Mar 14/2007 | | 5 | Mar 14/2007 | | 18 | Mar 14/2007 |
| | 2 | Mar 14/2007 | | 6 | Mar 14/2007 | W0630 | 1 | Mar 14/2007 |
| | 3 | Mar 14/2007 | | 7 | Mar 14/2007 | | 2 | Mar 14/2007 |
| | 4 | Mar 14/2007 | | 8 | Mar 14/2007 | | 3 | Mar 14/2007 |
| | 5 | Mar 14/2007 | | 9 | Mar 14/2007 | | 4 | Mar 14/2007 |
| | 6 | Mar 14/2007 | | 10 | Mar 14/2007 | | 5 | Mar 14/2007 |
| | 7 | Mar 14/2007 | | 11 | Mar 14/2007 | | 6 | Mar 14/2007 |
| | 8 | Mar 14/2007 | | 12 | Mar 14/2007 | | 7 | Mar 14/2007 |
| | 9 | Mar 14/2007 | | 13 | Mar 14/2007 | | 8 | Mar 14/2007 |
| | 10 | Mar 14/2007 | | 14 | Mar 14/2007 | | 9 | Mar 14/2007 |
| | 11 | Mar 14/2007 | W0620 | 1 | Mar 14/2007 | | 10 | Mar 14/2007 |
| | 12 | Mar 14/2007 | | 2 | Mar 14/2007 | | 11 | Mar 14/2007 |
| | 13 | Mar 14/2007 | | 3 | Mar 14/2007 | W0640 | 1 | Mar 14/2007 |
| | 14 | Mar 14/2007 | | 4 | Mar 14/2007 | | 2 | Mar 14/2007 |
| | 15 | Mar 14/2007 | | 5 | Mar 14/2007 | | 3 | Mar 14/2007 |
| | 16 | Mar 14/2007 | | 6 | Mar 14/2007 | | 4 | Mar 14/2007 |
| | 17 | Mar 14/2007 | | 7 | Mar 14/2007 | | 5 | Mar 14/2007 |
| | 18 | Mar 14/2007 | | 8 | Mar 14/2007 | | 6 | Mar 14/2007 |
| | 19 | Mar 14/2007 | | 9 | Mar 14/2007 | | 7 | Mar 14/2007 |
| | 20 | Mar 14/2007 | | 10 | Mar 14/2007 | | 8 | Mar 14/2007 |
| | 21 | Mar 14/2007 | | 11 | Mar 14/2007 | | 9 | Mar 14/2007 |
| | 22 | Mar 14/2007 | | 12 | Mar 14/2007 | | 10 | Mar 14/2007 |
| | 23 | Mar 14/2007 | | 13 | Mar 14/2007 | | 11 | Mar 14/2007 |
| W0610 | 1 | Mar 14/2007 | | 14 | Mar 14/2007 | | 12 | Mar 14/2007 |
| | 2 | Mar 14/2007 | | 15 | Mar 14/2007 | | 13 | Mar 14/2007 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 15
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date | |
|---------|------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|
| W0650 | 1 | Mar 14/2007 | W0660 cont. | 12 | Mar 14/2007 | W0690 cont. | 5 | Mar 09/2006 | |
| | 2 | Mar 14/2007 | | | | | 6 | Mar 09/2006 | |
| | 3 | Mar 14/2007 | | | | | 7 | Mar 09/2006 | |
| | 4 | Mar 14/2007 | | | | | W0700 | 1 | Mar 09/2006 |
| | 5 | Mar 14/2007 | | | | | | 2 | Mar 09/2006 |
| | 6 | Mar 14/2007 | | | | | | 3 | Mar 09/2006 |
| | 7 | Mar 14/2007 | | | | | | 4 | Mar 09/2006 |
| | 8 | Mar 14/2007 | | | | W0670 | 5 | Mar 09/2006 | |
| | 9 | Mar 14/2007 | 6 | Mar 09/2006 | | | | | |
| | 10 | Mar 14/2007 | 7 | Mar 09/2006 | | | | | |
| | 11 | Mar 14/2007 | 8 | Mar 09/2006 | | | | | |
| | 12 | Mar 14/2007 | 9 | Mar 09/2006 | | | | | |
| | 13 | Mar 14/2007 | 10 | Mar 09/2006 | | | | | |
| | 14 | Mar 14/2007 | 11 | Mar 09/2006 | | | | | |
| | 15 | Mar 14/2007 | W0680 | 12 | Mar 09/2006 | | | | |
| | 16 | Mar 14/2007 | | 13 | Mar 09/2006 | | | | |
| | 17 | Mar 14/2007 | | 14 | Mar 09/2006 | | | | |
| W0660 | 1 | Mar 14/2007 | | 15 | Mar 09/2006 | | | | |
| | 2 | Mar 14/2007 | | 16 | Mar 09/2006 | | | | |
| | 3 | Mar 14/2007 | | 17 | Mar 09/2006 | | | | |
| | 4 | Mar 14/2007 | | 18 | Mar 09/2006 | | | | |
| | 5 | Mar 14/2007 | | 19 | Mar 09/2006 | | | | |
| | 6 | Mar 14/2007 | 20 | Mar 09/2006 | | | | | |
| | 7 | Mar 14/2007 | 21 | Mar 09/2006 | | | | | |
| | 8 | Mar 14/2007 | 22 | Mar 09/2006 | | | | | |
| | 9 | Mar 14/2007 | 23 | Mar 09/2006 | | | | | |
| | 10 | Mar 14/2007 | W0690 | 1 | Mar 09/2006 | | | | |
| | 11 | Mar 14/2007 | | 2 | Mar 09/2006 | | | | |
| | | | 3 | Mar 09/2006 | W0710 | 1 | Mar 09/2006 | | |
| | | | 4 | Mar 09/2006 | | | | | |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 16
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0710 cont. | | | W0720 cont. | | | W0740 cont. | | |
| | 2 | Mar 09/2006 | | 8 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 9 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 10 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 5 | Mar 09/2006 | | 11 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 6 | Mar 09/2006 | | 12 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 7 | Mar 09/2006 | | 13 | Mar 09/2006 | | 9 | Mar 09/2006 |
| | 8 | Mar 09/2006 | | 14 | Mar 09/2006 | | 10 | Mar 09/2006 |
| | 9 | Mar 09/2006 | | 15 | Mar 09/2006 | W0750 | 1 | Mar 09/2006 |
| | 10 | Mar 09/2006 | | 16 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 11 | Mar 09/2006 | | 17 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 12 | Mar 09/2006 | W0730 | 1 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 13 | Mar 09/2006 | | 2 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 14 | Mar 09/2006 | | 3 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 15 | Mar 09/2006 | | 4 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 16 | Mar 09/2006 | | 5 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 17 | Mar 09/2006 | | 6 | Mar 09/2006 | | 9 | Mar 09/2006 |
| | 18 | Mar 09/2006 | | 7 | Mar 09/2006 | | 10 | Mar 09/2006 |
| | 19 | Mar 09/2006 | | 8 | Mar 09/2006 | | 11 | Mar 09/2006 |
| | 20 | Mar 09/2006 | | 9 | Mar 09/2006 | | 12 | Mar 09/2006 |
| | 21 | Mar 09/2006 | | 10 | Mar 09/2006 | | 13 | Mar 09/2006 |
| W0720 | 1 | Mar 09/2006 | | 11 | Mar 09/2006 | | 14 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 12 | Mar 09/2006 | | 15 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 13 | Mar 09/2006 | | 16 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 14 | Mar 09/2006 | | 17 | Mar 09/2006 |
| | 5 | Mar 09/2006 | W0740 | 1 | Mar 09/2006 | | 18 | Mar 09/2006 |
| | 6 | Mar 09/2006 | | 2 | Mar 09/2006 | | 19 | Mar 09/2006 |
| | 7 | Mar 09/2006 | | 3 | Mar 09/2006 | | 20 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 17
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0750 cont. | | | W0760 cont. | | | W0780 cont. | | |
| | 21 | Mar 09/2006 | | 21 | Mar 09/2006 | | 16 | Mar 09/2006 |
| | 22 | Mar 09/2006 | | 22 | Mar 09/2006 | | 17 | Mar 09/2006 |
| | 23 | Mar 09/2006 | | 23 | Mar 09/2006 | | 18 | Mar 09/2006 |
| | 24 | Mar 09/2006 | | 24 | Mar 09/2006 | | 19 | Mar 09/2006 |
| | 25 | Mar 09/2006 | W0770 | 1 | Mar 09/2006 | | 20 | Mar 09/2006 |
| | 26 | Mar 09/2006 | | 2 | Mar 09/2006 | | 21 | Mar 09/2006 |
| | 27 | Mar 09/2006 | | 3 | Mar 09/2006 | | 22 | Mar 09/2006 |
| W0760 | 1 | Mar 09/2006 | | 4 | Mar 09/2006 | | 23 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 5 | Mar 09/2006 | | 24 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 6 | Mar 09/2006 | W0790 | 1 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 7 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 5 | Mar 09/2006 | | 8 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 6 | Mar 09/2006 | W0780 | 1 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 7 | Mar 09/2006 | | 2 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 8 | Mar 09/2006 | | 3 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 9 | Mar 09/2006 | | 4 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 10 | Mar 09/2006 | | 5 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 11 | Mar 09/2006 | | 6 | Mar 09/2006 | | 9 | Mar 09/2006 |
| | 12 | Mar 09/2006 | | 7 | Mar 09/2006 | | 10 | Mar 09/2006 |
| | 13 | Mar 09/2006 | | 8 | Mar 09/2006 | | 11 | Mar 09/2006 |
| | 14 | Mar 09/2006 | | 9 | Mar 09/2006 | | 12 | Mar 09/2006 |
| | 15 | Mar 09/2006 | | 10 | Mar 09/2006 | | 13 | Mar 09/2006 |
| | 16 | Mar 09/2006 | | 11 | Mar 09/2006 | | 14 | Mar 09/2006 |
| | 17 | Mar 09/2006 | | 12 | Mar 09/2006 | | 15 | Mar 09/2006 |
| | 18 | Mar 09/2006 | | 13 | Mar 09/2006 | | 16 | Mar 09/2006 |
| | 19 | Mar 09/2006 | | 14 | Mar 09/2006 | W0800 | 1 | Mar 09/2006 |
| | 20 | Mar 09/2006 | | 15 | Mar 09/2006 | | 2 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES

Page 18
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0800 cont. | | | W0800 cont. | | | W0810 cont. | | |
| | 3 | Mar 09/2006 | | 30 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 31 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 5 | Mar 09/2006 | | 32 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 6 | Mar 09/2006 | | 33 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 7 | Mar 09/2006 | | 34 | Mar 09/2006 | | 9 | Mar 09/2006 |
| | 8 | Mar 09/2006 | | 35 | Mar 09/2006 | | 10 | Mar 09/2006 |
| | 9 | Mar 09/2006 | | 36 | Mar 09/2006 | | 11 | Mar 09/2006 |
| | 10 | Mar 09/2006 | | 37 | Mar 09/2006 | | 12 | Mar 09/2006 |
| | 11 | Mar 09/2006 | | 38 | Mar 09/2006 | | 13 | Mar 09/2006 |
| | 12 | Mar 09/2006 | | 39 | Mar 09/2006 | | 14 | Mar 09/2006 |
| | 13 | Mar 09/2006 | | 40 | Mar 09/2006 | | 15 | Mar 09/2006 |
| | 14 | Mar 09/2006 | | 41 | Mar 09/2006 | | 16 | Mar 09/2006 |
| | 15 | Mar 09/2006 | | 42 | Mar 09/2006 | | 17 | Mar 09/2006 |
| | 16 | Mar 09/2006 | | 43 | Mar 09/2006 | | 18 | Mar 09/2006 |
| | 17 | Mar 09/2006 | | 44 | Mar 09/2006 | | 19 | Mar 09/2006 |
| | 18 | Mar 09/2006 | | 45 | Mar 09/2006 | | 20 | Mar 09/2006 |
| | 19 | Mar 09/2006 | | 46 | Mar 09/2006 | | 21 | Mar 09/2006 |
| | 20 | Mar 09/2006 | | 47 | Mar 09/2006 | | 22 | Mar 09/2006 |
| | 21 | Mar 09/2006 | | 48 | Mar 09/2006 | | 23 | Mar 09/2006 |
| | 22 | Mar 09/2006 | | 49 | Mar 09/2006 | | 24 | Mar 09/2006 |
| | 23 | Mar 09/2006 | | 50 | Mar 09/2006 | | 25 | Mar 09/2006 |
| | 24 | Mar 09/2006 | | 51 | Mar 09/2006 | | 26 | Mar 09/2006 |
| | 25 | Mar 09/2006 | | 52 | Mar 09/2006 | | 27 | Mar 09/2006 |
| | 26 | Mar 09/2006 | W0810 | 1 | Mar 09/2006 | | 28 | Mar 09/2006 |
| | 27 | Mar 09/2006 | | 2 | Mar 09/2006 | | 29 | Mar 09/2006 |
| | 28 | Mar 09/2006 | | 3 | Mar 09/2006 | | 30 | Mar 09/2006 |
| | 29 | Mar 09/2006 | | 4 | Mar 09/2006 | | 31 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 19
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0810 cont. | | | W0810 cont. | | | W0810 cont. | | |
| | 32 | Mar 09/2006 | | 59 | Mar 09/2006 | | 86 | Mar 09/2006 |
| | 33 | Mar 09/2006 | | 60 | Mar 09/2006 | | 87 | Mar 09/2006 |
| | 34 | Mar 09/2006 | | 61 | Mar 09/2006 | | 88 | Mar 09/2006 |
| | 35 | Mar 09/2006 | | 62 | Mar 09/2006 | | 89 | Mar 09/2006 |
| | 36 | Mar 09/2006 | | 63 | Mar 09/2006 | | 90 | Mar 09/2006 |
| | 37 | Mar 09/2006 | | 64 | Mar 09/2006 | | 91 | Mar 09/2006 |
| | 38 | Mar 09/2006 | | 65 | Mar 09/2006 | | 92 | Mar 09/2006 |
| | 39 | Mar 09/2006 | | 66 | Mar 09/2006 | | 93 | Mar 09/2006 |
| | 40 | Mar 09/2006 | | 67 | Mar 09/2006 | | 94 | Mar 09/2006 |
| | 41 | Mar 09/2006 | | 68 | Mar 09/2006 | | 95 | Mar 09/2006 |
| | 42 | Mar 09/2006 | | 69 | Mar 09/2006 | | 96 | Mar 09/2006 |
| | 43 | Mar 09/2006 | | 70 | Mar 09/2006 | | 97 | Mar 09/2006 |
| | 44 | Mar 09/2006 | | 71 | Mar 09/2006 | | 98 | Mar 09/2006 |
| | 45 | Mar 09/2006 | | 72 | Mar 09/2006 | | 99 | Mar 09/2006 |
| | 46 | Mar 09/2006 | | 73 | Mar 09/2006 | | 100 | Mar 09/2006 |
| | 47 | Mar 09/2006 | | 74 | Mar 09/2006 | | 101 | Mar 09/2006 |
| | 48 | Mar 09/2006 | | 75 | Mar 09/2006 | | 102 | Mar 09/2006 |
| | 49 | Mar 09/2006 | | 76 | Mar 09/2006 | W0820 | 1 | Mar 09/2006 |
| | 50 | Mar 09/2006 | | 77 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 51 | Mar 09/2006 | | 78 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 52 | Mar 09/2006 | | 79 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 53 | Mar 09/2006 | | 80 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 54 | Mar 09/2006 | | 81 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 55 | Mar 09/2006 | | 82 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 56 | Mar 09/2006 | | 83 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 57 | Mar 09/2006 | | 84 | Mar 09/2006 | | 9 | Mar 09/2006 |
| | 58 | Mar 09/2006 | | 85 | Mar 09/2006 | | 10 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280T132

EFFECTIVE PAGES

Page 20
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|---------|------|-------------|-------------|------|-------------|
| W0820 cont. | | | W0850 | 1 | Mar 09/2006 | W0930 cont. | | |
| | 11 | Mar 09/2006 | | 2 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 12 | Mar 09/2006 | | 3 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 13 | Mar 09/2006 | | 4 | Mar 09/2006 | W0940 | 1 | Feb 06/2009 |
| | 14 | Mar 09/2006 | | 5 | Mar 09/2006 | | 2 | Feb 06/2009 |
| | 15 | Mar 09/2006 | W0860 | 1 | Mar 09/2006 | | 3 | Feb 06/2009 |
| | 16 | Mar 09/2006 | | 2 | Mar 09/2006 | | 4 | Feb 06/2009 |
| | 17 | Mar 09/2006 | | 3 | Mar 09/2006 | | 5 | Feb 06/2009 |
| | 18 | Mar 09/2006 | W0870 | 1 | Mar 09/2006 | | 6 | Feb 06/2009 |
| | 19 | Mar 09/2006 | | 2 | Mar 09/2006 | | 7 | Feb 06/2009 |
| | 20 | Mar 09/2006 | | 3 | Mar 09/2006 | | 8 | Feb 06/2009 |
| | 21 | Mar 09/2006 | W0880 | 1 | Mar 09/2006 | | 9 | Feb 06/2009 |
| | 22 | Mar 09/2006 | W0890 | 1 | Mar 09/2006 | | 10 | Feb 06/2009 |
| | 23 | Mar 09/2006 | | 2 | Mar 09/2006 | | 11 | Feb 06/2009 |
| | 24 | Mar 09/2006 | | 3 | Mar 09/2006 | | 12 | Feb 06/2009 |
| | 25 | Mar 09/2006 | | 4 | Mar 09/2006 | | 13 | Feb 06/2009 |
| | 26 | Mar 09/2006 | W0900 | 1 | Mar 09/2006 | | 14 | Feb 06/2009 |
| | 27 | Mar 09/2006 | | 2 | Mar 09/2006 | W0950 | 1 | Mar 09/2006 |
| | 28 | Mar 09/2006 | | 3 | Mar 09/2006 | | 2 | Mar 09/2006 |
| W0830 | 1 | Mar 09/2006 | | 4 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 2 | Mar 09/2006 | W0910 | 1 | Mar 09/2006 | W0960 | 1 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 2 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 3 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 5 | Mar 09/2006 | W0920 | 1 | Mar 09/2006 | | 4 | Mar 09/2006 |
| W0840 | 1 | Mar 09/2006 | | 2 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 3 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 3 | Mar 09/2006 | W0930 | 1 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 2 | Mar 09/2006 | | 8 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 21
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0960 cont. | | | W1030 cont. | | | W1050 cont. | | |
| | 9 | Mar 09/2006 | | 7 | Aug 15/2007 | | 8 | Mar 09/2006 |
| W0970 | 1 | Mar 09/2006 | | 8 | Aug 15/2007 | | 9 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 9 | Aug 15/2007 | | 10 | Mar 09/2006 |
| W0980 | 1 | Mar 09/2006 | | 10 | Aug 15/2007 | | 11 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 11 | Aug 15/2007 | W1060 | 1 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 12 | Aug 15/2007 | | 2 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 13 | Aug 15/2007 | | 3 | Mar 09/2006 |
| W0990 | 1 | Mar 09/2006 | | 14 | Aug 15/2007 | | 4 | Mar 09/2006 |
| W1000 | 1 | Mar 09/2006 | | 15 | Aug 15/2007 | | 5 | Mar 09/2006 |
| | 2 | Mar 09/2006 | W1040 | 1 | Mar 09/2006 | | 6 | Mar 09/2006 |
| W1010 | 1 | Mar 09/2006 | | 2 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 3 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 4 | Mar 09/2006 | | 9 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 5 | Mar 09/2006 | | 10 | Mar 09/2006 |
| | 5 | Mar 09/2006 | | 6 | Mar 09/2006 | | 11 | Mar 09/2006 |
| | 6 | Mar 09/2006 | | 7 | Mar 09/2006 | | 12 | Mar 09/2006 |
| W1020 | 1 | Mar 09/2006 | | 8 | Mar 09/2006 | | 13 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 9 | Mar 09/2006 | | 14 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 10 | Mar 09/2006 | | 15 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 11 | Mar 09/2006 | | 16 | Mar 09/2006 |
| | 5 | Mar 09/2006 | W1050 | 1 | Mar 09/2006 | | 17 | Mar 09/2006 |
| W1030 | 1 | Mar 09/2006 | | 2 | Mar 09/2006 | | 18 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 3 | Mar 09/2006 | | 19 | Mar 09/2006 |
| | 3 | Aug 15/2007 | | 4 | Mar 09/2006 | | 20 | Mar 09/2006 |
| | 4 | Aug 15/2007 | | 5 | Mar 09/2006 | | 21 | Mar 09/2006 |
| | 5 | Aug 15/2007 | | 6 | Mar 09/2006 | | 22 | Mar 09/2006 |
| | 6 | Aug 15/2007 | | 7 | Mar 09/2006 | | 23 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 22
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1060 cont. | | | W1060 cont. | | | W1060 cont. | | |
| | 24 | Mar 09/2006 | | 51 | Mar 09/2006 | | 78 | Mar 09/2006 |
| | 25 | Mar 09/2006 | | 52 | Mar 09/2006 | | 79 | Mar 09/2006 |
| | 26 | Mar 09/2006 | | 53 | Mar 09/2006 | | 80 | Mar 09/2006 |
| | 27 | Mar 09/2006 | | 54 | Mar 09/2006 | | 81 | Mar 09/2006 |
| | 28 | Mar 09/2006 | | 55 | Mar 09/2006 | | 82 | Mar 09/2006 |
| | 29 | Mar 09/2006 | | 56 | Mar 09/2006 | | 83 | Mar 09/2006 |
| | 30 | Mar 09/2006 | | 57 | Mar 09/2006 | W1070 | 1 | Mar 09/2006 |
| | 31 | Mar 09/2006 | | 58 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 32 | Mar 09/2006 | | 59 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 33 | Mar 09/2006 | | 60 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 34 | Mar 09/2006 | | 61 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 35 | Mar 09/2006 | | 62 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 36 | Mar 09/2006 | | 63 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 37 | Mar 09/2006 | | 64 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 38 | Mar 09/2006 | | 65 | Mar 09/2006 | | 9 | Mar 09/2006 |
| | 39 | Mar 09/2006 | | 66 | Mar 09/2006 | | 10 | Mar 09/2006 |
| | 40 | Mar 09/2006 | | 67 | Mar 09/2006 | | 11 | Mar 09/2006 |
| | 41 | Mar 09/2006 | | 68 | Mar 09/2006 | | 12 | Mar 09/2006 |
| | 42 | Mar 09/2006 | | 69 | Mar 09/2006 | W1080 | 1 | Mar 09/2006 |
| | 43 | Mar 09/2006 | | 70 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 44 | Mar 09/2006 | | 71 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 45 | Mar 09/2006 | | 72 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 46 | Mar 09/2006 | | 73 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 47 | Mar 09/2006 | | 74 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 48 | Mar 09/2006 | | 75 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 49 | Mar 09/2006 | | 76 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 50 | Mar 09/2006 | | 77 | Mar 09/2006 | | 9 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280T132

EFFECTIVE PAGES

Page 23
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1080 cont. | | | W1090 cont. | | | W1100 cont. | | |
| | 10 | Mar 09/2006 | | 13 | Mar 09/2006 | | 19 | Mar 09/2006 |
| | 11 | Mar 09/2006 | | 14 | Mar 09/2006 | | 20 | Mar 09/2006 |
| | 12 | Mar 09/2006 | | 15 | Mar 09/2006 | | 21 | Mar 09/2006 |
| | 13 | Mar 09/2006 | | 16 | Mar 09/2006 | | 22 | Mar 09/2006 |
| | 14 | Mar 09/2006 | | 17 | Mar 09/2006 | | 23 | Mar 09/2006 |
| | 15 | Mar 09/2006 | | 18 | Jun 06/2008 | | 24 | Mar 09/2006 |
| | 16 | Mar 09/2006 | | 19 | Mar 09/2006 | | 25 | Mar 09/2006 |
| | 17 | Mar 09/2006 | | 20 | Mar 09/2006 | | 26 | Mar 09/2006 |
| | 18 | Mar 09/2006 | | 21 | Mar 09/2006 | | 27 | Mar 09/2006 |
| | 19 | Mar 09/2006 | W1100 | 1 | Mar 09/2006 | | 28 | Mar 09/2006 |
| | 20 | Mar 09/2006 | | 2 | Mar 09/2006 | | 29 | Mar 09/2006 |
| | 21 | Mar 09/2006 | | 3 | Mar 09/2006 | | 30 | Mar 09/2006 |
| | 22 | Mar 09/2006 | | 4 | Mar 09/2006 | | 31 | Mar 09/2006 |
| | 23 | Mar 09/2006 | | 5 | Mar 09/2006 | | 32 | Mar 09/2006 |
| | 24 | Mar 09/2006 | | 6 | Mar 09/2006 | | 33 | Mar 09/2006 |
| W1090 | 1 | Mar 09/2006 | | 7 | Mar 09/2006 | | 34 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 8 | Mar 09/2006 | | 35 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 9 | Mar 09/2006 | | 36 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 10 | Mar 09/2006 | | 37 | Mar 09/2006 |
| | 5 | Mar 09/2006 | | 11 | Mar 09/2006 | | 38 | Mar 09/2006 |
| | 6 | Mar 09/2006 | | 12 | Mar 09/2006 | | 39 | Mar 09/2006 |
| | 7 | Mar 09/2006 | | 13 | Mar 09/2006 | | 40 | Mar 09/2006 |
| | 8 | Mar 09/2006 | | 14 | Mar 09/2006 | | 41 | Mar 09/2006 |
| | 9 | Mar 09/2006 | | 15 | Mar 09/2006 | | 42 | Mar 09/2006 |
| | 10 | Mar 09/2006 | | 16 | Mar 09/2006 | | 43 | Mar 09/2006 |
| | 11 | Mar 09/2006 | | 17 | Mar 09/2006 | | 44 | Mar 09/2006 |
| | 12 | Mar 09/2006 | | 18 | Mar 09/2006 | | 45 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280T132

EFFECTIVE PAGES

Page 24
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1100 cont. | | | W1110 cont. | | | W1130 cont. | | |
| | 46 | Mar 09/2006 | | 22 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 47 | Mar 09/2006 | | 23 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 48 | Mar 09/2006 | | 24 | Mar 09/2006 | | 9 | Mar 09/2006 |
| | 49 | Mar 09/2006 | | 25 | Mar 09/2006 | | 10 | Mar 09/2006 |
| | 50 | Mar 09/2006 | | 26 | Mar 09/2006 | | 11 | Mar 09/2006 |
| | 51 | Mar 09/2006 | | 27 | Mar 09/2006 | W1140 | 1 | Mar 09/2006 |
| W1110 | 1 | Mar 09/2006 | | 28 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 29 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 30 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 31 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 5 | Mar 09/2006 | | 32 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 6 | Mar 09/2006 | W1120 | 1 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 7 | Mar 09/2006 | | 2 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 8 | Mar 09/2006 | | 3 | Mar 09/2006 | | 9 | Mar 09/2006 |
| | 9 | Mar 09/2006 | | 4 | Mar 09/2006 | | 10 | Mar 09/2006 |
| | 10 | Mar 09/2006 | | 5 | Mar 09/2006 | | 11 | Mar 09/2006 |
| | 11 | Mar 09/2006 | | 6 | Mar 09/2006 | | 12 | Mar 09/2006 |
| | 12 | Mar 09/2006 | | 7 | Mar 09/2006 | | 13 | Mar 09/2006 |
| | 13 | Mar 09/2006 | | 8 | Mar 09/2006 | | 14 | Mar 09/2006 |
| | 14 | Mar 09/2006 | | 9 | Mar 09/2006 | | 15 | Mar 09/2006 |
| | 15 | Mar 09/2006 | | 10 | Mar 09/2006 | | 16 | Mar 09/2006 |
| | 16 | Mar 09/2006 | W1130 | 1 | Mar 09/2006 | | 17 | Mar 09/2006 |
| | 17 | Mar 09/2006 | | 2 | Mar 09/2006 | W1150 | 1 | Mar 09/2006 |
| | 18 | Feb 06/2009 | | 3 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 19 | Feb 06/2009 | | 4 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 20 | Feb 06/2009 | | 5 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 21 | Mar 09/2006 | | 6 | Mar 09/2006 | | 5 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 25
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1150 cont. | | | W1220 cont. | | | W1230 cont. | | |
| | 6 | Mar 09/2006 | | 3 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 7 | Mar 09/2006 | | 4 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 8 | Mar 09/2006 | | 5 | Mar 09/2006 | | 6 | Mar 09/2006 |
| W1160 | 1 | Mar 09/2006 | | 6 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 7 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 8 | Mar 09/2006 | | 9 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 9 | Mar 09/2006 | | 10 | Mar 09/2006 |
| | 5 | Mar 09/2006 | | 10 | Mar 09/2006 | | 11 | Mar 09/2006 |
| W1170 | 1 | Mar 09/2006 | | 11 | Mar 09/2006 | | 12 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 12 | Mar 09/2006 | | 13 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 13 | Mar 09/2006 | | 14 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 14 | Mar 09/2006 | | 15 | Mar 09/2006 |
| W1180 | 1 | Mar 09/2006 | | 15 | Mar 09/2006 | | 16 | Mar 09/2006 |
| W1190 | 1 | Mar 09/2006 | | 16 | Mar 09/2006 | | 17 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 17 | Mar 09/2006 | | 18 | Mar 09/2006 |
| W1200 | 1 | Mar 09/2006 | | 18 | Mar 09/2006 | | 19 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 19 | Mar 09/2006 | | 20 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 20 | Mar 09/2006 | | 21 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 21 | Mar 09/2006 | W1240 | 1 | Mar 09/2006 |
| | 5 | Mar 09/2006 | | 22 | Mar 09/2006 | | 2 | Mar 09/2006 |
| W1210 | 1 | Mar 09/2006 | | 23 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 24 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 25 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 26 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 5 | Mar 09/2006 | W1230 | 1 | Mar 09/2006 | | 7 | Mar 09/2006 |
| W1220 | 1 | Mar 09/2006 | | 2 | Mar 09/2006 | W1250 | 1 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 3 | Mar 09/2006 | | 2 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280T132

EFFECTIVE PAGES

Page 26
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1250 cont. | | | W1280 cont. | | | W1350 cont. | | |
| | 3 | Mar 09/2006 | | 4 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 5 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 5 | Mar 09/2006 | | 6 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 6 | Mar 09/2006 | | 7 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 7 | Mar 09/2006 | | 8 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 8 | Mar 09/2006 | | 9 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 9 | Mar 09/2006 | | 10 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 10 | Mar 09/2006 | | 11 | Mar 09/2006 | W1360 | 1 | Mar 09/2006 |
| | 11 | Mar 09/2006 | | 12 | Mar 09/2006 | W1370 | 1 | Mar 09/2006 |
| | 12 | Mar 09/2006 | | 13 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 13 | Mar 09/2006 | | 14 | Mar 09/2006 | W1380 | 1 | Mar 09/2006 |
| | 14 | Mar 09/2006 | | 15 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 15 | Mar 09/2006 | W1290 | 1 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 16 | Mar 09/2006 | | 2 | Mar 14/2007 | | 4 | Mar 09/2006 |
| | 17 | Mar 09/2006 | | 3 | Mar 09/2006 | W1390 | 1 | Mar 09/2006 |
| | 18 | Mar 09/2006 | W1300 | 1 | Mar 09/2006 | W1400 | 1 | Mar 09/2006 |
| | 19 | Mar 09/2006 | | 2 | Mar 09/2006 | | 2 | Mar 09/2006 |
| W1260 | 1 | Mar 09/2006 | | 3 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 2 | Mar 09/2006 | W1310 | 1 | Mar 09/2006 | W1410 | 1 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 2 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 3 | Mar 09/2006 | | 3 | Mar 09/2006 |
| W1270 | 1 | Mar 09/2006 | W1320 | 1 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 2 | Mar 09/2006 | W1330 | 1 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 2 | Mar 09/2006 | | 6 | Mar 09/2006 |
| W1280 | 1 | Mar 09/2006 | W1340 | 1 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 2 | Mar 09/2006 | | 8 | Mar 09/2006 |
| | 3 | Mar 09/2006 | W1350 | 1 | Mar 09/2006 | | 9 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST
D280T132

EFFECTIVE PAGES
Page 27
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|---------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1420 | 1 | Mar 09/2006 | W1520 cont. | | | W1630 cont. | | |
| W1430 | 1 | Mar 09/2006 | | 3 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 4 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 3 | Mar 09/2006 | W1530 | 1 | Mar 09/2006 | W1640 | 1 | Mar 09/2006 |
| W1440 | 1 | Mar 09/2006 | W1540 | 1 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 2 | Mar 09/2006 | W1660 | 1 | Mar 09/2006 |
| | 3 | Mar 09/2006 | W1560 | 1 | Mar 09/2006 | W1700 | 1 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 2 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 5 | Mar 09/2006 | W1570 | 1 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 6 | Mar 09/2006 | W1580 | 1 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 7 | Mar 09/2006 | W1590 | 1 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 8 | Mar 09/2006 | | 2 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 9 | Mar 09/2006 | | 3 | Mar 09/2006 | | 7 | Mar 09/2006 |
| W1460 | 1 | Mar 09/2006 | W1600 | 1 | Mar 09/2006 | | 8 | Mar 09/2006 |
| W1470 | 1 | Mar 09/2006 | | 2 | Mar 09/2006 | | 9 | Mar 09/2006 |
| W1480 | 1 | Mar 09/2006 | | 3 | Mar 09/2006 | | 10 | Mar 09/2006 |
| W1490 | 1 | Mar 09/2006 | | 4 | Mar 09/2006 | W1710 | 1 | Mar 09/2006 |
| W1500 | 1 | Mar 09/2006 | | 5 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 6 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 3 | Mar 09/2006 | W1610 | 1 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 2 | Mar 09/2006 | | 5 | Mar 09/2006 |
| W1510 | 1 | Mar 09/2006 | | 3 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 4 | Mar 09/2006 | W1720 | 1 | Mar 09/2006 |
| | 3 | Mar 09/2006 | | 5 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 4 | Mar 09/2006 | | 6 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 5 | Mar 09/2006 | W1630 | 1 | Mar 09/2006 | | 4 | Mar 09/2006 |
| W1520 | 1 | Mar 09/2006 | | 2 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 2 | Mar 09/2006 | | 3 | Mar 09/2006 | | 6 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280T132

EFFECTIVE PAGES

Page 28
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date | | | | | | |
|---------|------|-------------|-------------|------|-------------|-------------|------|-------------|--|---|-------------|--|----|-------------|
| W1730 | 1 | Mar 09/2006 | W2000 cont. | 4 | Mar 09/2006 | W2000 cont. | 31 | Jun 06/2008 | | | | | | |
| | 2 | Mar 09/2006 | | | | | | | | | | | | |
| W1760 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| W1770 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| W1790 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| W1800 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| | 2 | Mar 09/2006 | | | | | | | | | | | | |
| | 3 | Mar 09/2006 | | | | | | | | | | | | |
| W1810 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| | 2 | Mar 09/2006 | | | | | | | | | | | | |
| | 3 | Mar 09/2006 | | | | | | | | | | | | |
| W1820 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| | 2 | Mar 09/2006 | | | | | | | | | | | | |
| W1830 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| | 2 | Mar 09/2006 | | | | | | | | | | | | |
| W1840 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| | 2 | Mar 09/2006 | | | | | | | | | | | | |
| W1850 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| | 2 | Mar 09/2006 | | | | | | | | | | | | |
| W1860 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| W1890 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| W1900 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| W1910 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| W1920 | 1 | Aug 15/2007 | | | | | | | | | | | | |
| W1930 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| W2000 | 1 | Mar 09/2006 | | | | | | | | | | | | |
| | 2 | Mar 09/2006 | | | | | | | | | | | | |
| | 3 | Mar 09/2006 | | | | | | | | | | | | |
| | | | | | | | | | | 5 | Mar 09/2006 | | 32 | Jun 06/2008 |
| | | | | | | | | | | 6 | Mar 09/2006 | | 33 | Mar 09/2006 |
| | | | | 7 | Mar 09/2006 | | 34 | Mar 09/2006 | | | | | | |
| | | | | 8 | Mar 09/2006 | | 35 | Mar 09/2006 | | | | | | |
| | | | | 9 | Mar 09/2006 | | 36 | Mar 09/2006 | | | | | | |
| | | | | 10 | Mar 09/2006 | | 37 | Mar 09/2006 | | | | | | |
| | | | | 11 | Mar 09/2006 | | 38 | Mar 09/2006 | | | | | | |
| | | | | 12 | Mar 09/2006 | | 39 | Mar 09/2006 | | | | | | |
| | | | | 13 | Mar 09/2006 | | 40 | Mar 09/2006 | | | | | | |
| | | | | 14 | Mar 09/2006 | | 41 | Mar 09/2006 | | | | | | |
| | | | | 15 | Mar 09/2006 | | 42 | Mar 09/2006 | | | | | | |
| | | | | 16 | Mar 09/2006 | | 43 | Mar 09/2006 | | | | | | |
| | | | | 17 | Jun 06/2008 | | 44 | Mar 09/2006 | | | | | | |
| | | | | 18 | Jun 06/2008 | | 45 | Mar 09/2006 | | | | | | |
| | | | | 19 | Jun 06/2008 | | 46 | Mar 09/2006 | | | | | | |
| | | | | 20 | Jun 06/2008 | | 47 | Mar 09/2006 | | | | | | |
| | | | | 21 | Jun 06/2008 | | 48 | Mar 09/2006 | | | | | | |
| | | | | 22 | Jun 06/2008 | | 49 | Mar 09/2006 | | | | | | |
| | | | | 23 | Jun 06/2008 | | 50 | Mar 09/2006 | | | | | | |
| | | | | 24 | Jun 06/2008 | | 51 | Mar 09/2006 | | | | | | |
| | | | | 25 | Jun 06/2008 | | 52 | Mar 09/2006 | | | | | | |
| | | | | 26 | Jun 06/2008 | | 53 | Mar 09/2006 | | | | | | |
| | | | | 27 | Jun 06/2008 | | 54 | Mar 09/2006 | | | | | | |
| | | | | 28 | Jun 06/2008 | | 55 | Mar 09/2006 | | | | | | |
| | | | | 29 | Jun 06/2008 | | 56 | Mar 09/2006 | | | | | | |
| | | | | 30 | Jun 06/2008 | | 57 | Mar 09/2006 | | | | | | |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280T132

EFFECTIVE PAGES

Page 29
Aug 05/2009



91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|---------|------|-------------|
| W2000 cont. | | | W2050 cont. | | | W3510 | 1 | Feb 06/2009 |
| | 58 | Mar 09/2006 | | 2 | Mar 09/2006 | | 2 | Feb 06/2009 |
| | 59 | Mar 09/2006 | | 3 | Mar 09/2006 | W3520 | 1 | Mar 09/2006 |
| | 60 | Mar 09/2006 | | 4 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 61 | Mar 09/2006 | W2060 | 1 | Mar 09/2006 | W3530 | 1 | Mar 09/2006 |
| | 62 | Mar 09/2006 | | 2 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 63 | Mar 09/2006 | | 3 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 64 | Mar 09/2006 | | 4 | Mar 09/2006 | W3540 | 1 | Mar 09/2006 |
| | 65 | Mar 09/2006 | | 5 | Mar 09/2006 | W5150 | 1 | Mar 09/2006 |
| | 66 | Mar 09/2006 | | 6 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 67 | Mar 09/2006 | | 7 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 68 | Mar 09/2006 | W2100 | 1 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 69 | Mar 09/2006 | W2110 | 1 | Mar 09/2006 | | 5 | Mar 09/2006 |
| | 70 | Mar 09/2006 | W2210 | 1 | Mar 09/2006 | | 6 | Mar 09/2006 |
| | 71 | Mar 09/2006 | | 2 | Mar 09/2006 | | 7 | Mar 09/2006 |
| | 72 | Mar 09/2006 | W3000 | 1 | Mar 09/2006 | W9000 | 1 | Mar 09/2006 |
| | 73 | Mar 09/2006 | | 2 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 74 | Mar 09/2006 | | 3 | Mar 09/2006 | | 3 | Mar 09/2006 |
| | 75 | Mar 09/2006 | | 4 | Mar 09/2006 | | 4 | Mar 09/2006 |
| | 76 | Mar 09/2006 | W3010 | 1 | Mar 09/2006 | W9010 | 1 | Mar 09/2006 |
| | 77 | Mar 09/2006 | | 2 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 78 | Mar 09/2006 | W3500 | 1 | Mar 09/2006 | W9020 | 1 | Mar 09/2006 |
| | 79 | Mar 09/2006 | | 2 | Mar 09/2006 | | 2 | Mar 09/2006 |
| | 80 | Mar 09/2006 | | 3 | Mar 09/2006 | | 3 | Mar 09/2006 |
| W2010 | 1 | Mar 09/2006 | | 4 | Mar 09/2006 | | 4 | Mar 09/2006 |
| W2020 | 1 | Mar 09/2006 | | 5 | Mar 09/2006 | | 5 | Mar 09/2006 |
| W2040 | 1 | Mar 09/2006 | | 6 | Mar 09/2006 | | 6 | Mar 09/2006 |
| W2050 | 1 | Mar 09/2006 | | 7 | Feb 06/2009 | | 7 | Mar 09/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280T132

EFFECTIVE PAGES

Page 30
Aug 05/2009

91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|---------|------|------|
| W9020 cont. | | | W9120 cont. | | | | | |
| | 8 | Mar 09/2006 | | 2 | Mar 09/2006 | | | |
| | 9 | Mar 09/2006 | W9150 | 1 | Mar 09/2006 | | | |
| W9030 | 1 | Mar 09/2006 | W9160 | 1 | Mar 09/2006 | | | |
| | 2 | Mar 09/2006 | W9510 | 1 | Mar 09/2006 | | | |
| W9040 | 1 | Mar 09/2006 | | 2 | BLANK | | | |
| | 2 | Mar 09/2006 | | | | | | |
| | 3 | Mar 09/2006 | | | | | | |
| W9050 | 1 | Mar 09/2006 | | | | | | |
| | 2 | Mar 09/2006 | | | | | | |
| | 3 | Mar 09/2006 | | | | | | |
| | 4 | Mar 09/2006 | | | | | | |
| W9060 | 1 | Mar 09/2006 | | | | | | |
| | 2 | Mar 09/2006 | | | | | | |
| | 3 | Mar 09/2006 | | | | | | |
| W9070 | 1 | Mar 09/2006 | | | | | | |
| | 2 | Mar 09/2006 | | | | | | |
| | 3 | Mar 09/2006 | | | | | | |
| | 4 | Mar 09/2006 | | | | | | |
| | 5 | Mar 09/2006 | | | | | | |
| | 6 | Mar 09/2006 | | | | | | |
| | 7 | Mar 09/2006 | | | | | | |
| | 8 | Mar 09/2006 | | | | | | |
| W9080 | 1 | Mar 09/2006 | | | | | | |
| W9090 | 1 | Mar 09/2006 | | | | | | |
| | 2 | Mar 09/2006 | | | | | | |
| W9110 | 1 | Mar 09/2006 | | | | | | |
| W9120 | 1 | Mar 09/2006 | | | | | | |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280T132

EFFECTIVE PAGES

Page 31
Aug 05/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL | | | | | | | | | | | | | | | | |
| 001 | 22 | | PA | | 6-11 | 34-22-82 | D00113 | | 40 | | | | | | D04163P | | 1 | | | ALL |
| 002 | 20 | | PA | | 6-4 | 34-22-82 | D00113 | | 38 | | | | | | GD00057 | A.. | 2 | | | 050-099 |
| 002 | 20 | | PA | | 7-0 | 34-22-82 | D00113 | | 38 | | | | | | GD00057 | A.. | 2 | | | 150-199, 275-299 |
| 003 | 20 | | PA | | 6-7 | 34-22-82 | D00113 | | 20 | | | | | | GD00061 | S.. | 2 | | | 050-099 |
| 003 | 20 | | PA | | 7-0 | 34-22-82 | D00113 | | 20 | | | | | | GD00061 | S.. | 2 | | | 150-199, 275-299 |
| 004 | 20 | | PA | | 6-5 | 34-22-82 | D00113 | | CAP | Y | | | | | GD00063 | D.. | 2 | | | 050-099 |
| 004 | 20 | | PA | | 7-0 | 34-22-82 | D00113 | | CAP | Y | | | | | GD00063 | D.. | 2 | | | 150-199, 275-299 |
| 005 | 24 | | PK | | 5-3 | 34-22-82 | D00113 | | 34 | | | | | | D04283P | | 4 | | | 050-099 |
| 005 | 24 | | PK | | 7-0 | 34-22-82 | D00113 | | 31 | | | | | | D04283P | | 4 | | | 150-199, 275-299 |
| 006 | 20 | | PA | | 4-4 | 34-22-82 | D04283P | | 5 | | | | | | GD00063 | D.. | 2 | | | 050-099 |
| 006 | 20 | | PA | | 5-0 | 34-22-82 | D04283P | | 5 | | | | | | GD00063 | D.. | 2 | | | 150-199, 275-299 |
| 007 | 24 | | PV | AG | 5-0 | 34-22-81 | D00645 | | 54 | | | | | | TB0241X | D005 | BJ | | | ALL |
| 007Z | | | | AG | 0-0 | 34-22-81 | D00645 | | DED | | | | | | TB0241X | DED | | | | ALL |
| 008 | 20 | | PA | | 4-0 | 34-22-81 | D00645 | | 55 | | | | | | GD00057 | A.. | 2 | | | ALL |
| 009 | 20 | | PA | | 4-0 | 34-22-81 | D00645 | | 6 | | | | | | GD00061 | S.. | 2 | | | ALL |
| 010 | 20 | | PA | | 4-0 | 34-22-81 | D00645 | | 3 | | | | | | GD00063 | D.. | 2 | | | ALL |
| 011 | 20 | | PA | | 4-0 | 34-22-81 | D00645 | | 28 | | | | | | GD00061 | S.. | 2 | | | ALL |
| 014 | 20 | | PA | | 4-4 | 34-22-17 | D04283P | | 10 | | | | | | GD00063 | D.. | 2 | | | 050-099 |
| 014 | 20 | | PA | | 5-0 | 34-22-17 | D04283P | | 10 | | | | | | GD00063 | D.. | 2 | | | 150-199, 275-299 |
| 015 | 24 | | PK | | 5-1 | 34-22-17 | D04283P | | 11 | | | | | | D04167P | | 2 | | | 050-099 |
| 015 | 24 | | PK | | 6-0 | 34-22-17 | D04283P | | 11 | | | | | | D04167P | | 2 | | | 150-199, 275-299 |
| 016 | 20 | | PA | | 4-4 | 34-22-17 | D04283P | | 12 | | | | | | GD00063 | D.. | 2 | | | 050-099 |
| 016 | 20 | | PA | | 5-0 | 34-22-17 | D04283P | | 12 | | | | | | GD00063 | D.. | 2 | | | 150-199, 275-299 |
| 017 | 24 | | PK | | 5-1 | 34-22-17 | D04283P | | 13 | | | | | | D04167P | | 3 | | | 050-099 |
| 017 | 24 | | PK | | 6-0 | 34-22-17 | D04283P | | 13 | | | | | | D04167P | | 3 | | | 150-199, 275-299 |
| 018 | 24 | | PK | | 5-1 | 34-22-17 | D04283P | | 14 | | | | | | D04167P | | 4 | | | 050-099 |
| 018 | 24 | | PK | | 6-0 | 34-22-17 | D04283P | | 14 | | | | | | D04167P | | 4 | | | 150-199, 275-299 |
| 019 | 20 | | PA | | 4-4 | 34-22-17 | D04283P | | 15 | | | | | | GD00063 | D.. | 2 | | | 050-099 |
| 019 | 20 | | PA | | 5-0 | 34-22-17 | D04283P | | 15 | | | | | | GD00063 | D.. | 2 | | | 150-199, 275-299 |
| 01J | 22 | | PQ | AE | 13-0 | 34-12-61 | D04283P | | 40 | | | | | | TB0243X | D003 | BJ | | | ALL |
| 01JZ | | | | AE | 0-0 | 34-12-61 | D04283P | | DED | | | | | | TB0243X | DED | | | | ALL |
| 01K | 22 | | PA | | 6-0 | 34-12-61 | D05255P | | 53 | | | | | | D04283P | | 42 | | | ALL |
| 01L | 22 | | PA | | 6-0 | 34-12-61 | D05255P | | 54 | | | | | | D04283P | | 43 | | | ALL |
| 020 | 22 | | PA | | 5-0 | 34-22-17 | D04283P | | 16 | | | | | | D04147P | | 4 | | | 050-099 |
| 020 | 22 | | PA | | 6-0 | 34-22-17 | D04283P | | 16 | | | | | | D04147P | | 4 | | | 150-199, 275-299 |
| 022 | 20 | | PA | | 4-4 | 34-22-17 | D04283P | | 21 | | | | | | GD00063 | D.. | 2 | | | 050-099 |
| 022 | 20 | | PA | | 5-0 | 34-22-17 | D04283P | | 21 | | | | | | GD00063 | D.. | 2 | | | 150-199, 275-299 |
| 024 | 24 | | PK | | 3-11 | 34-22-16 | D04163P | | 3 | | | | | | D05809P | | 6 | | | ALL |
| 025 | 24 | | PK | | 3-11 | 34-22-16 | D04163P | | 4 | | | | | | D05809P | | 5 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 1

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 026 | 24 | | PK | 5-1 | 34-22-38 | D04283P | | 6 | | D04167P | | 1 | | | 050-099 |
| 026 | 24 | | PK | 6-0 | 34-22-38 | D04283P | | 6 | | D04167P | | 1 | | | 150-199, 275-299 |
| 028 | 24 | | PK | 7-7 | 22-14-11 | D00633 | | 7 | | D04173P | | 16 | | | 050-099 |
| 028 | 24 | | PK | 7-9 | 22-14-11 | D00633 | | 7 | | D04173P | | 16 | | | 150-199, 275-299 |
| 029 | 24 | | PK | 7-6 | 22-14-11 | D01363 | | 7 | | D04167P | | 47 | | | 050-099 |
| 029 | 24 | | PK | 7-9 | 22-14-11 | D01363 | | 7 | | D04167P | | 47 | | | 150-199, 275-299 |
| 031 | 24 | | PK | 7-6 | 22-14-11 | D01363 | | 5 | | D04167P | | 49 | | | 050-099 |
| 031 | 24 | | PK | 7-9 | 22-14-11 | D01363 | | 5 | | D04167P | | 49 | | | 150-199, 275-299 |
| 032 | 20 | | PA | 4-10 | 33-13-11 | D01363 | | 13 | | GD03698 | A.. | 2 | | | 050-099 |
| 032 | 20 | | PA | 4-9 | 33-13-11 | D01363 | | 13 | | GD03698 | A.. | 2 | | | 150-199, 275-299 |
| 033 | 20 | | PA | 6-10 | 22-14-11 | D01363 | | 12 | | GD00061 | S.. | 2 | | | 050-099 |
| 033 | 20 | | PA | 6-9 | 22-14-11 | D01363 | | 12 | | GD00061 | S.. | 2 | | | 150-199, 275-299 |
| 034 | 20 | | PA | 6-8 | 22-14-11 | D01363 | | 11 | | GD00063 | D.. | 2 | | | 050-099 |
| 034 | 20 | | PA | 6-9 | 22-14-11 | D01363 | | 11 | | GD00063 | D.. | 2 | | | 150-199, 275-299 |
| 035 | 24 | | PK | 7-7 | 22-14-11 | D00633 | | 5 | | D04173P | | 17 | | | 050-099 |
| 035 | 24 | | PK | 7-9 | 22-14-11 | D00633 | | 5 | | D04173P | | 17 | | | 150-199, 275-299 |
| 036 | 24 | | PK | 7-6 | 22-14-11 | D01363 | | 9 | | D04167P | | 48 | | | 050-099 |
| 036 | 24 | | PK | 7-9 | 22-14-11 | D01363 | | 9 | | D04167P | | 48 | | | 150-199, 275-299 |
| 038 | 24 | | PK | 3-6 | 34-13-21 | D05255P | | 44 | | TB0241Y | A008 | BJ | | | 050-099 |
| 038 | 24 | | PK | 5-0 | 34-13-21 | D05255P | | 44 | | TB0241Y | A008 | BJ | | | 150-199, 275-299 |
| 040 | 24 | | PK | 7-1 | 34-13-21 | D00111 | | 12 | | TB0241Y | A008 | BJ | | | 050-099 |
| 040 | 24 | | PK | 8-0 | 34-13-21 | D00111 | | 12 | | TB0241Y | A008 | BJ | | | 150-199, 275-299 |
| 041 | 22 | | PA | 4-0 | 34-32-11 | D04285P | | 1 | | SM00045 | | W | | | 050-099 |
| 041 | 22 | | PA | 5-0 | 34-32-11 | D04285P | | 1 | | SM00045 | | W | | | 150-199, 275-299 |
| 042 | 22 | | PA | 4-0 | 34-32-11 | D04285P | | 2 | | SM00046 | | W | | | 050-099 |
| 042 | 22 | | PA | 5-0 | 34-32-11 | D04285P | | 2 | | SM00046 | | W | | | 150-199, 275-299 |
| 043 | 22 | | PA | 4-0 | 34-32-11 | D04285P | | 3 | | SM00047 | | W | | | 050-099 |
| 043 | 22 | | PA | 5-0 | 34-32-11 | D04285P | | 3 | | SM00047 | | W | | | 150-199, 275-299 |
| 044 | 20 | | PA | 3-9 | 34-13-11 | D00101 | | 10 | | GD00063 | D.. | 2 | | | 050-099 |
| 044 | 20 | | PA | 4-0 | 34-13-11 | D00101 | | 10 | | GD00063 | D.. | 2 | | | 150-199, 275-299 |
| 045 | 20 | | PA | 3-10 | 34-13-11 | D00101 | | 7 | | GD00061 | S.. | 2 | | | 050-099 |
| 045 | 20 | | PA | 4-0 | 34-13-11 | D00101 | | 7 | | GD00061 | S.. | 2 | | | 150-199, 275-299 |
| 046 | 20 | | PA | 3-7 | 34-13-11 | D00101 | | 4 | | GD00057 | A.. | 2 | | | 050-099 |
| 046 | 20 | | PA | 4-0 | 34-13-11 | D00101 | | 4 | | GD00057 | A.. | 2 | | | 150-199, 275-299 |
| 047 | 22 | | PA | 4-2 | 34-13-11 | D00101 | | 3 | | D04163P | | 5 | | | ALL |
| 048 | 22 | | PA | 6-10 | 34-13-11 | D00111 | | 3 | | D04163P | | 6 | | | ALL |
| 049 | 20 | | PA | 6-3 | 34-13-11 | D00111 | | 4 | | GD00057 | A.. | 2 | | | 050-099 |
| 049 | 20 | | PA | 7-0 | 34-13-11 | D00111 | | 4 | | GD00057 | A.. | 2 | | | 150-199, 275-299 |
| 050 | 20 | | PA | 6-4 | 34-13-11 | D00111 | | 10 | | GD00063 | D.. | 2 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 2

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|---------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | | |
| 050 | 20 | | PA | | 7-0 34-13-11 | D00111 | | 10 | | | | | GD00063 | D.. | 2 | | 150-199, 275-299 |
| 051 | 20 | | PA | | 6-6 34-13-11 | D00111 | | 7 | | | | | GD00061 | S.. | 2 | | 050-099 |
| 051 | 20 | | PA | | 7-0 34-13-11 | D00111 | | 7 | | | | | GD00061 | S.. | 2 | | 150-199, 275-299 |
| 056 | 24 | | PK | | 11-6 31-25-11 | D00103 | | 8 | | | | | TB0243X | A003 | BJ | | ALL |
| 057 | 24 | | PK | | 7-3 31-25-11 | D00103 | | 3 | | | | | D04163P | | 7 | | ALL |
| 058 | 20 | | PA | | 6-11 31-25-11 | D00103 | | 7 | | | | | GD00061 | S.. | 2 | | 050-099 |
| 058 | 20 | | PA | | 7-0 31-25-11 | D00103 | | 7 | | | | | GD00061 | S.. | 2 | | 150-199, 275-299 |
| 059 | 20 | | PA | | 6-9 31-25-11 | D00103 | | 4 | | | | | GD00063 | D.. | 2 | | 050-099 |
| 059 | 20 | | PA | | 7-0 31-25-11 | D00103 | | 4 | | | | | GD00063 | D.. | 2 | | 150-199, 275-299 |
| 060 | 20 | | PA | | 6-9 31-25-11 | D00103 | | 9 | | | | | GD00063 | D.. | 2 | | 050-099 |
| 060 | 20 | | PA | | 7-0 31-25-11 | D00103 | | 9 | | | | | GD00063 | D.. | 2 | | 150-199, 275-299 |
| 061 | 22 | | PA | | 7-6 22-14-11 | D01363 | | 1 | | | | | D04167P | | 5 | | 050-099 |
| 061 | 22 | | PA | | 7-9 22-14-11 | D01363 | | 1 | | | | | D04167P | | 5 | | 150-199, 275-299 |
| 062 | 22 | | PA | | 7-7 22-14-11 | D00633 | | 1 | | | | | D04173P | | 13 | | 050-099 |
| 062 | 22 | | PA | | 7-9 22-14-11 | D00633 | | 1 | | | | | D04173P | | 13 | | 150-199, 275-299 |
| 063 | 24 | | PK | | 11-0 34-22-81 | D00647 | | 21 | | | | | TB0241Y | C001 | BJ | | ALL |
| 064 | 24 | | PK | | 4-1 34-22-18 | TB0241Y | | | C001 | BJ | | | D05809P | | 7 | | 050-099 |
| 064 | 24 | | PK | | 5-0 34-22-18 | TB0241Y | | | C001 | BJ | | | D05809P | | 7 | | 150-199, 275-299 |
| 065 | 24 | | PK | | 5-0 34-22-81 | D00645 | | 21 | | | | | TB0241Y | C001 | BJ | | ALL |
| 066 | 24 | | PV | CP | 5-0 34-22-81 | D00645 | | 29 | | | | | TB0241Y | A013 | BJ | | ALL |
| 066Z | | | | CP | 0-0 34-22-81 | D00645 | | | DED | | | | TB0241Y | DED | | | ALL |
| 071 | 20 | | PA | | 6-10 22-14-11 | D00633 | | 11 | | | | | GD00061 | S.. | 2 | | ALL |
| 075 | 24 | | PK | | 3-11 34-22-16 | D04163P | | 8 | | | | | D05809P | | 4 | | ALL |
| 076 | 24 | | PK | | 8-9 34-22-18 | D00157 | | 27 | | | | | TB0241Y | C001 | BJ | | 050-099 |
| 076 | 24 | | PK | | 9-0 34-22-18 | D00157 | | 27 | | | | | TB0241Y | C001 | BJ | | 150-199, 275-299 |
| 077 | 24 | | PK | | 9-3 34-22-18 | D00157 | | 26 | | | | | D05809P | | 8 | | 050-099 |
| 077 | 24 | | PK | | 10-0 34-22-18 | D00157 | | 26 | | | | | D05809P | | 8 | | 150-199, 275-299 |
| 079 | 24 | | PK | | 9-8 34-22-91 | D04283P | | 18 | | | | | D00647 | | 16 | | 050-099 |
| 079 | 24 | | PK | | 10-0 34-22-91 | D04283P | | 18 | | | | | D00647 | | 16 | | 150-199, 275-299 |
| 080 | 20 | | PA | | 4-4 34-22-91 | D04283P | | 19 | | | | | GD00063 | D.. | 2 | | 050-099 |
| 080 | 20 | | PA | | 5-0 34-22-91 | D04283P | | 19 | | | | | GD00063 | D.. | 2 | | 150-199, 275-299 |
| 081 | 24 | | PK | | 10-0 34-22-37 | D04283P | | 7 | | | | | D05043P | | 3 | | ALL |
| 082 | 20 | | PA | | 4-4 34-22-37 | D04283P | | 8 | | | | | GD00063 | D.. | 2 | | 050-099 |
| 082 | 20 | | PA | | 5-0 34-22-37 | D04283P | | 8 | | | | | GD00063 | D.. | 2 | | 150-199, 275-299 |
| 084 | 22 | | PQ | DI | 10-1 33-16-13 | D04285P | | 5 | | | | | D04560P | | 3 | | 050-099 |
| 084 | 22 | | PQ | DI | 11-0 33-16-13 | D04285P | | 5 | | | | | D04560P | | 3 | | 150-199, 275-299 |
| 084Z | | | | DI | 0-0 33-16-13 | D04285P | | | DED | | | | D04560P | DED | | | ALL |
| 087 | 22 | | PQ | DL | 12-0 33-16-13 | TB0243Y | | | C016 | BJ | | | D00111 | | 11 | | ALL |
| 087Z | | | | DL | 0-0 33-16-13 | TB0243Y | | | DED | | | | D00111 | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 3

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 088 | 22 | PA | | | 12-0 | 33-16-13 | TB0247Z | 9 | BJ | | D00111 | 9 | | | ALL |
| 091 | 24 | PK | | | 5-1 | 32-42-11 | D04283P | 2 | | | D04167P | 44 | | | 050-099 |
| 091 | 24 | PK | | | 6-0 | 32-42-11 | D04283P | 2 | | | D04167P | 44 | | | 150-199, 275-299 |
| 092 | 20 | PA | | | 4-6 | 32-42-11 | D04283P | 1 | | | GD00061 | D.. | 2 | | 050-099 |
| 092 | 20 | PA | | | 5-0 | 32-42-11 | D04283P | 1 | | | GD00061 | D.. | 2 | | 150-199, 275-299 |
| 093 | 22 | PQ | DR | | 10-0 | 33-16-16 | D00475 | 3 | | | D04560P | 8 | | | 050-099 |
| 093 | 22 | PQ | DR | | 11-0 | 33-16-16 | D00475 | 3 | | | D04560P | 8 | | | 150-199, 275-299 |
| 093Z | | | DR | | 0-0 | 33-16-16 | D00475 | | DED | | D04560P | DED | | | ALL |
| 094 | 22 | PA | | | 10-0 | 33-16-16 | D00475 | 9 | | | TB0247Z | 9 | BJ | | ALL |
| 095 | 22 | PQ | DT | | 8-6 | 33-16-16 | D00869 | 4 | | | TB0245Y | A003 | BJ | | 050-099 |
| 095 | 22 | PQ | DT | | 9-0 | 33-16-16 | D00869 | 4 | | | TB0245Y | A003 | BJ | | 150-199, 275-299 |
| 095Z | | | DT | | 0-0 | 33-16-16 | D00869 | | DED | | TB0245Y | DED | | | ALL |
| 096 | 22 | PQ | DU | | 8-6 | 33-16-16 | D00869 | 5 | | | TB0245Z | 5 | BJ | | 050-099 |
| 096 | 22 | PQ | DU | | 9-0 | 33-16-16 | D00869 | 5 | | | TB0245Z | 5 | BJ | | 150-199, 275-299 |
| 096Z | | | DU | | 0-0 | 33-16-16 | D00869 | | DED | | TB0245Z | DED | | | ALL |
| 098 | 24 | PK | | | 4-9 | 31-51-21 | TB0241Y | A007 | BJ | | D05014J | 8 | | | 050-099 |
| 098 | 24 | PK | | | 6-0 | 31-51-21 | TB0241Y | A007 | BJ | | D05014J | 8 | | | 150-199, 275-299 |
| 099 | 24 | PK | | | 3-6 | 31-51-21 | D05255P | 42 | | | TB0241Y | A007 | BJ | | 050-099 |
| 099 | 24 | PK | | | 4-0 | 31-51-21 | D05255P | 42 | | | TB0241Y | A007 | BJ | | 150-199, 275-299 |
| 101 | 24 | PK | | | 4-8 | 31-51-21 | D05255P | 43 | | | D05014J | 7 | | | 050-099 |
| 101 | 24 | PK | | | 6-0 | 31-51-21 | D05255P | 43 | | | D05014J | 7 | | | 150-199, 275-299 |
| 102 | 22 | PA | | | 3-1 | 34-32-11 | D04147P | 5 | | | SM00045 | | W | | 050-099 |
| 102 | 22 | PA | | | 4-0 | 34-32-11 | D04147P | 5 | | | SM00045 | | W | | 150-199, 275-299 |
| 103 | 22 | PA | | | 3-1 | 34-32-11 | D04147P | 6 | | | SM00046 | | W | | 050-099 |
| 103 | 22 | PA | | | 4-0 | 34-32-11 | D04147P | 6 | | | SM00046 | | W | | 150-199, 275-299 |
| 104 | 22 | PA | | | 3-1 | 34-32-11 | D04147P | 7 | | | SM00047 | | W | | 050-099 |
| 104 | 22 | PA | | | 4-0 | 34-32-11 | D04147P | 7 | | | SM00047 | | W | | 150-199, 275-299 |
| 105 | 22 | PA | | | 8-10 | 34-32-11 | D05043P | 7 | | | SM00045 | | W | | 050-099 |
| 105 | 22 | PA | | | 9-0 | 34-32-11 | D05043P | 7 | | | SM00045 | | W | | 150-199, 275-299 |
| 106 | 22 | PA | | | 8-10 | 34-32-11 | D05043P | 6 | | | SM00046 | | W | | 050-099 |
| 106 | 22 | PA | | | 9-0 | 34-32-11 | D05043P | 6 | | | SM00046 | | W | | 150-199, 275-299 |
| 107 | 22 | PA | | | 8-10 | 34-32-11 | D05043P | 5 | | | SM00047 | | W | | 050-099 |
| 107 | 22 | PA | | | 9-0 | 34-32-11 | D05043P | 5 | | | SM00047 | | W | | 150-199, 275-299 |
| 108 | 20 | PA | | | 4-10 | 33-13-11 | D01363 | 3 | | | SP00343 | 9 | | | 050-099 |
| 108 | 20 | PA | | | 6-7 | 33-13-11 | D01363 | 3 | | | SP00343 | 9 | | | 150-199, 275-299 |
| 109 | 22 | PA | | | 5-0 | 34-12-61 | D04283P | 36 | | | D04147P | 39 | | | 050-099 |
| 109 | 22 | PA | | | 6-0 | 34-12-61 | D04283P | 36 | | | D04147P | 39 | | | 150-199, 275-299 |
| 110 | 20 | PA | | | 4-6 | 33-13-11 | D00111 | 1 | | | SP00343 | 9 | | | 050-099 |
| 110 | 20 | PA | | | 6-0 | 33-13-11 | D00111 | 1 | | | SP00343 | 9 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 4

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | | |
| 111 | 20 | | PA | 4-6 | 33-13-11 | D00111 | | 2 | | | | | GD03698 | A.. | 2 | | 050-099 |
| 111 | 20 | | PA | 6-0 | 33-13-11 | D00111 | | 2 | | | | | GD03698 | A.. | 2 | | 150-199, 275-299 |
| 112 | 20 | | PA | 4-7 | 33-13-11 | D00113 | | 42 | | | | | SP00343 | | 9 | | 050-099 |
| 112 | 20 | | PA | 6-0 | 33-13-11 | D00113 | | 42 | | | | | SP00343 | | 9 | | 150-199, 275-299 |
| 113 | 20 | | PA | 4-7 | 33-13-11 | D00113 | | 43 | | | | | GD03698 | A.. | 2 | | 050-099 |
| 113 | 20 | | PA | 6-0 | 33-13-11 | D00113 | | 43 | | | | | GD03698 | A.. | 2 | | 150-199, 275-299 |
| 115 | 20 | | PA | 4-11 | 33-13-11 | D00103 | | 2 | | | | | GD03698 | A.. | 2 | | 050-099 |
| 115 | 20 | | PA | 5-0 | 33-13-11 | D00103 | | 2 | | | | | GD03698 | A.. | 2 | | 150-199, 275-299 |
| 116 | 18 | | PA | 3-0 | 33-13-11 | D04283P | | 22 | DK | | | | SP00355 | | 9 | | 050-099 |
| 116 | 18 | | PA | 5-0 | 33-13-11 | D04283P | | 22 | DK | | | | SPZ0002 | | S | | 150, 152-199, 275-299 |
| 116 | 18 | | PA | 4-0 | 33-13-11 | D04283P | | 22 | DK | | | | SP00355 | | 9 | | 151 |
| 117 | 18 | | PA | 4-1 | 33-13-11 | D04283P | | 23 | DK | | | | GD00059 | A.. | 2 | | 050-099 |
| 117 | 18 | | PA | 5-0 | 33-13-11 | D04283P | | 23 | DK | | | | GD00059 | A.. | 2 | | 150-199, 275-299 |
| 118 | 20 | | PA | 3-7 | 33-13-11 | D00101 | | 1 | | | | | SP00355 | | 9 | | 050-099 |
| 118 | 20 | | PA | 5-0 | 33-13-11 | D00101 | | 1 | | | | | SP00355 | | 9 | | 150-199, 275-278 |
| 119 | 20 | | PA | 3-6 | 33-13-11 | D00101 | | 2 | | | | | GD00059 | A.. | 2 | | 050-099 |
| 119 | 20 | | PA | 5-0 | 33-13-11 | D00101 | | 2 | | | | | GD00059 | A.. | 2 | | 150-199, 275-278 |
| 120 | 16 | | PA | 4-0 | 33-13-11 | D00645 | | 1 | FM | | | | SP00345 | | 9 | | ALL |
| 121 | 16 | | PA | 4-0 | 33-13-11 | D00645 | | 2 | FM | | | | GD00059 | A.. | 2 | | ALL |
| 122 | 24 | | PK | 5-0 | 33-13-11 | TB0247Z | | 14 | BJ | | | | D05395P | | 12 | | ALL |
| 131 | 24 | | PV | FF | 8-11 | 32-61-14 | D05305P | 23 | | | | | D05395P | | 35 | | 050-099 |
| 131 | 24 | | PV | FF | 9-0 | 32-61-14 | D05305P | 23 | | | | | D05395P | | 35 | | 150-199, 275-299 |
| 131Z | | | | FF | 0-0 | 32-61-14 | D05305P | DED | | | | | D05395P | DED | | | ALL |
| 132 | 24 | | PV | FG | 8-11 | 32-61-14 | D05305P | 24 | | | | | D05395P | | 36 | | 050-099 |
| 132 | 24 | | PV | FG | 9-0 | 32-61-14 | D05305P | 24 | | | | | D05395P | | 36 | | 150-199, 275-299 |
| 132Z | | | | FG | 0-0 | 32-61-14 | D05305P | DED | | | | | D05395P | DED | | | ALL |
| 133 | 24 | | PV | FH | 8-11 | 32-61-14 | D05305P | 25 | | | | | D05395P | | 37 | | 050-099 |
| 133 | 24 | | PV | FH | 9-0 | 32-61-14 | D05305P | 25 | | | | | D05395P | | 37 | | 150-199, 275-299 |
| 133Z | | | | FH | 0-0 | 32-61-14 | D05305P | DED | | | | | D05395P | DED | | | ALL |
| 134 | 22 | | PA | 11-10 | 30-33-11 | D00299 | | 1 | | | | | D04560P | | 13 | | 050-099 |
| 134 | 22 | | PA | 12-0 | 30-33-11 | D00299 | | 1 | | | | | D04560P | | 13 | | 150-199, 275-299 |
| 135 | 22 | | PA | 3-10 | 30-33-11 | D00299 | | 6 | | | | | D04173P | | 14 | | 050-099 |
| 135 | 22 | | PA | 5-0 | 30-33-11 | D00299 | | 6 | | | | | D04173P | | 14 | | 150-199, 275-299 |
| 136 | 20 | | PA | 3-1 | 34-12-11 | D00299 | | 7 | | | | | GD00061 | D.. | 2 | | 050-099 |
| 136 | 20 | | PA | 4-0 | 34-12-11 | D00299 | | 7 | | | | | GD00061 | D.. | 2 | | 150-199, 275-299 |
| 137 | 20 | | PA | 4-6 | 34-12-61 | GD00061 | | D.. | 2 | | | | D04283P | | 24 | | 050-099 |
| 137 | 20 | | PA | 5-0 | 34-12-61 | GD00061 | | D.. | 2 | | | | D04283P | | 24 | | 150-199, 275-299 |
| 138 | 20 | | PA | 4-6 | 34-12-61 | GD00061 | | D.. | 2 | | | | D04283P | | 25 | | 050-099 |
| 138 | 20 | | PA | 5-0 | 34-12-61 | GD00061 | | D.. | 2 | | | | D04283P | | 25 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 5

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 139 | 20 | | PA | | 4-6 | 34-12-61 | GD00061 | D.. | 2 | | D04283P | 26 | | | 050-099 |
| 139 | 20 | | PA | | 5-0 | 34-12-61 | GD00061 | D.. | 2 | | D04283P | 26 | | | 150-199, 275-299 |
| 143 | 24 | | PK | | 5-0 | 34-12-61 | D04147P | | 37 | | D04283P | 30 | | | 050-099 |
| 143 | 24 | | PK | | 6-0 | 34-12-61 | D04147P | | 37 | | D04283P | 30 | | | 150-199, 275-299 |
| 144 | 22 | | PA | | 2-5 | 34-13-11 | D00101 | | 8 | | SM00051 | | W | | 050-099 |
| 144 | 22 | | PA | | 3-0 | 34-13-11 | D00101 | | 8 | | SM00051 | | W | | 150-199, 275-299 |
| 145 | 22 | | PA | | 2-6 | 34-13-11 | D04283P | | 31 | | SM00051 | | W | | 050-099 |
| 145 | 22 | | PA | | 4-0 | 34-13-11 | D04283P | | 31 | | SM00051 | | W | | 150-199, 275-299 |
| 146 | 22 | | PA | | 4-0 | 34-13-11 | D00111 | | 8 | | SM00051 | | W | | 050-099 |
| 146 | 22 | | PA | | 5-0 | 34-13-11 | D00111 | | 8 | | SM00051 | | W | | 150-199, 275-299 |
| 151 | 24 | | PK | | 5-1 | 22-41-13 | D04283P | | 38 | | D04167P | 50 | | | 050-099 |
| 151 | 24 | | PK | | 6-0 | 22-41-13 | D04283P | | 38 | | D04167P | 50 | | | 150-199, 275-299 |
| 152 | 24 | | PK | | 5-1 | 22-41-13 | D04283P | | 37 | | D04167P | 52 | | | 050-099 |
| 152 | 24 | | PK | | 6-0 | 22-41-13 | D04283P | | 37 | | D04167P | 52 | | | 150-199, 275-299 |
| 153 | 24 | | PK | | 11-6 | 22-41-13 | D05043P | | 4 | | D04167P | 51 | | | 050-099 |
| 153 | 24 | | PK | | 11-0 | 22-41-13 | D05043P | | 4 | | D04167P | 51 | | | 150-199, 275-299 |
| 154 | 20 | | PA | | 4-6 | 22-41-13 | D04283P | | 39 | | GD00061 | D.. | 2 | | 050-099 |
| 154 | 20 | | PA | | 5-0 | 22-41-13 | D04283P | | 39 | | GD00061 | D.. | 2 | | 150-199, 275-299 |
| 155 | 22 | | PA | | 5-1 | 34-22-16 | D04283P | | 32 | | D04167P | 43 | | | 050-099 |
| 155 | 22 | | PA | | 6-0 | 34-22-16 | D04283P | | 32 | | D04167P | 43 | | | 150-199, 275-299 |
| 156 | 20 | | PA | | 4-4 | 34-22-16 | D04283P | | 33 | | GD00063 | D.. | 2 | | 050-099 |
| 156 | 20 | | PA | | 5-0 | 34-22-16 | D04283P | | 33 | | GD00063 | D.. | 2 | | 150-199, 275-299 |
| 162 | 24 | | PK | | 5-1 | 34-22-17 | D04167P | | 42 | | D04283P | 17 | | | 050-099 |
| 162 | 24 | | PK | | 6-0 | 34-22-17 | D04167P | | 42 | | D04283P | 17 | | | 150-199, 275-299 |
| 167 | 22 | | PA | | 10-0 | 33-16-13 | TB0247Z | | 9 | BJ | D04285P | 8 | | | ALL |
| 172 | 22 | | PA | | 10-0 | 29-21-32 | D05395P | | 17 | | D04285P | 17 | | | 050-099 |
| 172 | 22 | | PA | | 11-0 | 29-21-32 | D05395P | | 17 | | D04285P | 17 | | | 150-199, 275-299 |
| 173 | 20 | | PA | | 9-0 | 29-21-32 | GD00071 | D.. | 2 | | D04285P | 10 | | | ALL |
| 175 | 22 | | PA | | 10-0 | 29-21-32 | D05395P | | 20 | | D04285P | 12 | | | 050-099 |
| 175 | 22 | | PA | | 11-0 | 29-21-32 | D05395P | | 20 | | D04285P | 12 | | | 150-199, 275-299 |
| 176 | 22 | | PA | | 10-0 | 29-21-32 | D05395P | | 22 | | D04285P | 13 | | | 050-099 |
| 176 | 22 | | PA | | 11-0 | 29-21-32 | D05395P | | 22 | | D04285P | 13 | | | 150-199, 275-299 |
| 177 | 22 | | PA | | 10-0 | 29-21-32 | D05395P | | 23 | | D04285P | 14 | | | 050-099 |
| 177 | 22 | | PA | | 11-0 | 29-21-32 | D05395P | | 23 | | D04285P | 14 | | | 150-199, 275-299 |
| 178 | 22 | | PA | | 6-10 | 29-21-32 | D04163P | | 9 | | D04285P | 15 | | | ALL |
| 181 | 22 | | PA | | 10-0 | 29-21-32 | D04285P | | 22 | | D05395P | 18 | | | 050-099 |
| 181 | 22 | | PA | | 11-0 | 29-21-32 | D04285P | | 22 | | D05395P | 18 | | | 150-199, 275-299 |
| 183 | 20 | | PA | | 4-6 | 33-13-11 | D04285P | | 6 | | SP00343 | | 9 | | 050-099 |
| 183 | 20 | | PA | | 5-0 | 33-13-11 | D04285P | | 6 | | SP00343 | | 9 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 6

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 184 | 20 | | PA | 4-6 | 33-13-11 | D04285P | 7 | | | | GD03698 | A.. | 2 | | 050-099 |
| 184 | 20 | | PA | 4-0 | 33-13-11 | D04285P | 7 | | | | GD03698 | A.. | 2 | | 150-199, 275-299 |
| 187 | 24 | | PK | 5-1 | 34-22-17 | D04167P | 6 | | | | D04283P | 9 | | | 050-099 |
| 187 | 24 | | PK | 6-0 | 34-22-17 | D04167P | 6 | | | | D04283P | 9 | | | 150-199 |
| 187 | 24 | | PK | 6-0 | 34-22-17 | D04283P | 9 | | | | D04167P | 6 | | | 275-299 |
| 188 | 22 | | PA | 7-2 | 22-34-11 | D04285P | 28 | | | | D04167P | 54 | | | 050-099 |
| 188 | 22 | | PA | 8-0 | 22-34-11 | D04285P | 28 | | | | D04167P | 54 | | | 150-199, 275-299 |
| 194 | 24 | | PK | 5-0 | 33-13-18 | D05395P | 8 | | | | TB0247Z | 14 | BJ | | ALL |
| 201B | 24 | | PW IA | 11-4 | 34-22-91 | D00647 | 42 | | | | D04171P | 20 | | | 050-099 |
| 201B | 24 | | PW IA | 12-0 | 34-22-91 | D00647 | 42 | | | | D04171P | 20 | | | 150-199, 275-299 |
| 201R | 24 | | PW IA | 0-0 | 34-22-91 | D00647 | 41 | | | | D04171P | 19 | | | ALL |
| 201Z | | | IA | 0-0 | 34-22-91 | D00647 | DED | | | | D04171P | 21 | | | ALL |
| 202B | 24 | | PW IB | 7-3 | 34-22-82 | D00113 | 48 | | | | D04167P | 28 | | | 050-099 |
| 202B | 24 | | PW IB | 8-0 | 34-22-82 | D00113 | 48 | | | | D04167P | 28 | | | 150-199, 275-299 |
| 202R | 24 | | PW IB | 0-0 | 34-22-82 | D00113 | 47 | | | | D04167P | 27 | | | ALL |
| 202Z | | | IB | 0-0 | 34-22-82 | D00113 | DED | | | | D04167P | 29 | | | ALL |
| 204B | 22 | | PB ID | 7-1 | 34-12-21 | D00111 | 28 | | | | D04147P | 30 | | | 050-099 |
| 204B | 22 | | PB ID | 9-0 | 34-12-21 | D00111 | 28 | | | | D04147P | 30 | | | 150-199, 275-299 |
| 204R | 22 | | PB ID | 0-0 | 34-12-21 | D00111 | 27 | | | | D04147P | 29 | | | ALL |
| 205B | 24 | | PW IE | 8-6 | 34-22-91 | D00647 | 19 | | | | SM00008 | | W | | 050-099 |
| 205B | 24 | | PW IE | 9-0 | 34-22-91 | D00647 | 19 | | | | SM00008 | | W | | 150-199, 275-299 |
| 205R | 24 | | PW IE | 0-0 | 34-22-91 | D00647 | 18 | | | | SM00007 | | W | | ALL |
| 205Z | | | IE | 0-0 | 34-22-91 | D00647 | DED | | | | SM00007 | REF | | FC | ALL |
| 206B | 24 | | PW IF | 8-6 | 34-22-91 | D00647 | 10 | | | | SM00018 | | W | | 050-099 |
| 206B | 24 | | PW IF | 9-0 | 34-22-91 | D00647 | 10 | | | | SM00018 | | W | | 150-199, 275-299 |
| 206R | 24 | | PW IF | 0-0 | 34-22-91 | D00647 | 9 | | | | SM00017 | | W | | ALL |
| 206Z | | | IF | 0-0 | 34-22-91 | D00647 | DED | | | | SM00017 | REF | | FE | ALL |
| 207B | 24 | | PW IG | 8-6 | 34-22-91 | D00647 | 39 | | | | SM00033 | | W | | 050-099 |
| 207B | 24 | | PW IG | 9-0 | 34-22-91 | D00647 | 39 | | | | SM00033 | | W | | 150-199, 275-299 |
| 207R | 24 | | PW IG | 0-0 | 34-22-91 | D00647 | 38 | | | | SM00032 | | W | | ALL |
| 207Z | | | IG | 0-0 | 34-22-91 | D00647 | DED | | | | SM00032 | REF | | FG | ALL |
| 209B | 24 | | PW II | 7-4 | 34-22-82 | D00113 | 45 | | | | D04173P | 2 | | | 050-099 |
| 209B | 24 | | PW II | 9-0 | 34-22-82 | D00113 | 45 | | | | D04173P | 2 | | | 150-199, 275-299 |
| 209R | 24 | | PW II | 0-0 | 34-22-82 | D00113 | 26 | | | | D04173P | 1 | | | ALL |
| 209Z | | | II | 0-0 | 34-22-82 | D00113 | DED | | | | D04173P | 3 | | | ALL |
| 211B | 24 | | PW IK | 3-0 | 34-22-81 | D00645 | 19 | | | | SM00008 | | W | | ALL |
| 211R | 24 | | PW IK | 0-0 | 34-22-81 | D00645 | 18 | | | | SM00007 | | W | | ALL |
| 211Z | | | IK | 0-0 | 34-22-81 | D00645 | DED | | | | SM00007 | REF | | FC | ALL |
| 212B | 24 | | PW IL | 3-1 | 34-22-81 | D04147P | 2 | | | | SM00008 | | W | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 7

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 212B | 24 | PW | IL | | 4-0 | 34-22-81 | D04147P | | 2 | | SM00008 | | W | | 150-199, 275-299 |
| 212R | 24 | PW | IL | | 0-0 | 34-22-81 | D04147P | | 1 | | SM00007 | | W | | ALL |
| 212Z | | | IL | | 0-0 | 34-22-81 | D04147P | | 3 | | SM00007 | REF | | FC | ALL |
| 214B | 24 | PW | IN | | 6-0 | 34-22-81 | TB0241X | D012 | BJ | | D00645 | 42 | | | ALL |
| 214R | 24 | PW | IN | | 0-0 | 34-22-81 | TB0241X | D011 | BJ | | D00645 | 41 | | | ALL |
| 214Z | | | IN | | 0-0 | 34-22-81 | TB0241X | C012 | BJ | | D00645 | DED | | | ALL |
| 215B | 24 | PW | IO | | 6-0 | 34-22-81 | D00645 | | 45 | | TB0241Y | C008 | BJ | | ALL |
| 215R | 24 | PW | IO | | 0-0 | 34-22-81 | D00645 | | 44 | | TB0241Y | C007 | BJ | | ALL |
| 215Z | | | IO | | 0-0 | 34-22-81 | D00645 | | DED | | TB0241Y | | | FM | ALL |
| 216B | 24 | PW | IP | | 3-10 | 34-22-81 | D04173P | | 7 | | TB0241Y | C008 | BJ | | 050-099 |
| 216B | 24 | PW | IP | | 5-0 | 34-22-81 | D04173P | | 7 | | TB0241Y | C008 | BJ | | 150-199, 275-299 |
| 216R | 24 | PW | IP | | 0-0 | 34-22-81 | D04173P | | 6 | | TB0241Y | C007 | BJ | | ALL |
| 216Z | | | IP | | 0-0 | 34-22-81 | D04173P | | 8 | | TB0241Y | | | FM | ALL |
| 217B | 24 | PW | IQ | | 3-0 | 34-22-81 | D00645 | | 39 | | SM00033 | | W | | ALL |
| 217R | 24 | PW | IQ | | 0-0 | 34-22-81 | D00645 | | 38 | | SM00032 | | W | | ALL |
| 217Z | | | IQ | | 0-0 | 34-22-81 | D00645 | | DED | | SM00032 | REF | | FG | ALL |
| 218B | 24 | PW | IR | | 13-0 | 34-22-81 | D00645 | | 14 | | TB0243Y | C010 | BJ | | ALL |
| 218R | 24 | PW | IR | | 0-0 | 34-22-81 | D00645 | | 13 | | TB0243Y | C009 | BJ | | ALL |
| 218Z | | | IR | | 0-0 | 34-22-81 | D00645 | | DED | | TB0243Y | | | IR | ALL |
| 219B | 24 | PW | IS | | 13-0 | 34-22-81 | D00645 | | 49 | | TB0243Y | A010 | BJ | | ALL |
| 219R | 24 | PW | IS | | 0-0 | 34-22-81 | D00645 | | 48 | | TB0243Y | A009 | BJ | | ALL |
| 219Z | | | IS | | 0-0 | 34-22-81 | D00645 | | DED | | TB0243Y | | | IS | ALL |
| 220B | 24 | PW | IT | | 3-0 | 34-22-81 | D00645 | | 10 | | SM00018 | | W | | ALL |
| 220R | 24 | PW | IT | | 0-0 | 34-22-81 | D00645 | | 9 | | SM00017 | | W | | ALL |
| 220Z | | | IT | | 0-0 | 34-22-81 | D00645 | | DED | | SM00017 | REF | | FE | ALL |
| 221B | 24 | PW | IU | | 3-2 | 34-22-81 | D04167P | | 11 | | SM00018 | | W | | 050-099 |
| 221B | 24 | PW | IU | | 4-0 | 34-22-81 | D04167P | | 11 | | SM00018 | | W | | 150-156, 162-166 |
| 221B | 24 | PW | IU | | 4-0 | 34-22-81 | D05255P | | 51 | | SM00018 | | W | | 157, 167-199, 275-299 |
| 221R | 24 | PW | IU | | 0-0 | 34-22-81 | D04167P | | 10 | | SM00017 | | W | | 050-099, 150-156, 162-166 |
| 221R | 24 | PW | IU | | 0-0 | 34-22-81 | D05255P | | 50 | | SM00017 | | W | | 157, 167-199, 275-299 |
| 221Z | | | IU | | 0-0 | 34-22-81 | D04167P | | 12 | | SM00017 | REF | | FE | 050-099, 150-156, 162-166 |
| 221Z | | | IU | | 0-0 | 34-22-81 | D05255P | | 52 | | SM00017 | REF | | FE | 157, 167-199, 275-299 |
| 222B | 24 | PW | IV | | 3-2 | 34-22-81 | D04167P | | 14 | | SM00033 | | W | | 050-099 |
| 222B | 24 | PW | IV | | 4-0 | 34-22-81 | D04167P | | 14 | | SM00033 | | W | | 150-199, 275-299 |
| 222R | 24 | PW | IV | | 0-0 | 34-22-81 | D04167P | | 13 | | SM00032 | | W | | ALL |
| 222Z | | | IV | | 0-0 | 34-22-81 | D04167P | | 15 | | SM00032 | REF | | FG | ALL |
| 228B | 24 | PW | JC | | 4-5 | 22-14-11 | D00101 | | 25 | | TB0245Z | 2 | BJ | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0010
Page 8
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | | |
| 228B | 24 | PW | JC | 5-0 | 22-14-11 | D00101 | | 25 | | | | | | | | | 150-199, 275-299 |
| 228R | 24 | PW | JC | 0-0 | 22-14-11 | D00101 | | 24 | | | | | | | | | ALL |
| 228Z | | | JC | 0-0 | 22-14-11 | D00101 | | DED | | | | | | JC | | | ALL |
| 229 | 20 | UA | | 1-6 | 22-14-11 | D00475 | | | | JD | | | | S.. | 2 | | 050-099 |
| 229 | 20 | UA | | 3-0 | 22-14-11 | D00475 | | | | JD | | | | S.. | 2 | | 150-199, 275-299 |
| 229B | 24 | PW | JD | 8-0 | 22-14-11 | D00475 | | 27 | | | | | | 2 | BJ | | ALL |
| 229R | 24 | PW | JD | 0-0 | 22-14-11 | D00475 | | 26 | | | | | | 1 | BJ | | ALL |
| 229Z | | | JD | 0-0 | 22-14-11 | D00475 | | | | JD | | | | REF | | JC | ALL |
| 230B | 24 | PW | JE | 3-6 | 22-14-11 | D05255P | | 40 | | | | | | 2 | BJ | | 050-099 |
| 230B | 24 | PW | JE | 4-0 | 22-14-11 | D05255P | | 40 | | | | | | 2 | BJ | | 150-199, 275-299 |
| 230R | 24 | PW | JE | 0-0 | 22-14-11 | D05255P | | 39 | | | | | | 1 | BJ | | ALL |
| 230Z | | | JE | 0-0 | 22-14-11 | D05255P | | 41 | | | | | | REF | | JC | ALL |
| 231B | 24 | PW | JF | 13-0 | 34-13-21 | D04171P | | 6 | | | | | | A006 | BJ | | ALL |
| 231R | 24 | PW | JF | 0-0 | 34-13-21 | D04171P | | 5 | | | | | | A005 | BJ | | ALL |
| 231Z | | | JF | 0-0 | 34-13-21 | D04171P | | 7 | | | | | | B004 | BJ | | ALL |
| 232B | 24 | PW | JG | 2-5 | 34-13-11 | D00101 | | 31 | | | | | | | W | | 050-099 |
| 232B | 24 | PW | JG | 3-0 | 34-13-11 | D00101 | | 31 | | | | | | | W | | 150-199, 275-299 |
| 232R | 24 | PW | JG | 0-0 | 34-13-11 | D00101 | | 30 | | | | | | | W | | ALL |
| 232Z | | | JG | 0-0 | 34-13-11 | D00101 | | DED | | | | | | REF | | FV | ALL |
| 233B | 24 | PW | JH | 4-0 | 34-13-11 | D00111 | | 31 | | | | | | | W | | 050-099 |
| 233B | 24 | PW | JH | 5-0 | 34-13-11 | D00111 | | 31 | | | | | | | W | | 150-199, 275-299 |
| 233R | 24 | PW | JH | 0-0 | 34-13-11 | D00111 | | 30 | | | | | | | W | | ALL |
| 233Z | | | JH | 0-0 | 34-13-11 | D00111 | | DED | | | | | | REF | | FV | ALL |
| 234B | 24 | PW | JI | 3-2 | 34-13-11 | D04167P | | 22 | | | | | | | W | | 050-099 |
| 234B | 24 | PW | JI | 4-0 | 34-13-11 | D04167P | | 22 | | | | | | | W | | 150-199, 275-299 |
| 234R | 24 | PW | JI | 0-0 | 34-13-11 | D04167P | | 21 | | | | | | | W | | ALL |
| 234Z | | | JI | 0-0 | 34-13-11 | D04167P | | 23 | | | | | | REF | | FV | ALL |
| 235B | 24 | PW | JJ | 7-6 | 31-25-11 | D00103 | | 23 | | | | | | 14 | | | ALL |
| 235R | 24 | PW | JJ | 0-0 | 31-25-11 | D00103 | | 24 | | | | | | 13 | | | ALL |
| 235Z | | | JJ | 0-0 | 31-25-11 | D00103 | | DED | | | | | | 15 | | | ALL |
| 236B | 22 | PR | JK | 7-10 | 34-12-11 | D00111 | | 23 | | | | | | 7 | | | 050-099 |
| 236B | 22 | PR | JK | 9-0 | 34-12-11 | D00111 | | 23 | | | | | | 7 | | | 150-199, 275-299 |
| 236R | 22 | PR | JK | 0-0 | 34-12-11 | D00111 | | 22 | | | | | | 6 | | | ALL |
| 236Z | | | JK | 0-0 | 34-12-11 | D00111 | | DED | | | | | | DED | | | ALL |
| 241B | 24 | PW | JP | 11-0 | 34-22-91 | D00647 | | 45 | | | | | | C008 | BJ | | 050-099 |
| 241B | 24 | PW | JP | 12-0 | 34-22-91 | D00647 | | 45 | | | | | | C008 | BJ | | 150-199, 275-299 |
| 241R | 24 | PW | JP | 0-0 | 34-22-91 | D00647 | | 44 | | | | | | C007 | BJ | | ALL |
| 241Z | | | JP | 0-0 | 34-22-91 | D00647 | | DED | | | | | | | | FM | ALL |
| 242 | 20 | UA | | 7-5 | 22-32-12 | D01669 | | | | JQ | | | | S.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 9

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | |
| 242 | 20 | | UA | | 8-0 | 22-32-12 | D01669 | | | | JQ | GD03700 | S.. | 2 | | 150-199, 275-299 |
| 242B | 24 | | PW | JQ | 9-4 | 22-32-12 | D01669 | | 29 | | | D05255P | | 16 | | 050-099 |
| 242B | 24 | | PW | JQ | 10-0 | 22-32-12 | D01669 | | 29 | | | D05255P | | 16 | | 150-199, 275-299 |
| 242R | 24 | | PW | JQ | 0-0 | 22-32-12 | D01669 | | 28 | | | D05255P | | 15 | | ALL |
| 242Z | | | | JQ | 0-0 | 22-32-12 | D01669 | | | | JQ | D05255P | | 17 | | ALL |
| 246B | 20 | | PR | JU | 3-8 | 34-12-11 | D00299 | | 4 | | | D04167P | | 40 | | 050-099 |
| 246B | 20 | | PR | JU | 5-0 | 34-12-11 | D00299 | | 4 | | | D04167P | | 40 | | 150-199, 275-299 |
| 246R | 20 | | PR | JU | 0-0 | 34-12-11 | D00299 | | 3 | | | D04167P | | 39 | | ALL |
| 246Z | | | | JU | 0-0 | 34-12-11 | D00299 | | DED | | | D04167P | | 41 | | ALL |
| 248B | 24 | | PW | JW | 4-5 | 34-13-11 | D00101 | | 27 | | | TB0241Y | C010 | BJ | | 050-099 |
| 248B | 24 | | PW | JW | 5-0 | 34-13-11 | D00101 | | 27 | | | TB0241Y | C010 | BJ | | 150-199, 275-299 |
| 248R | 24 | | PW | JW | 0-0 | 34-13-11 | D00101 | | 26 | | | TB0241Y | C009 | BJ | | ALL |
| 248Z | | | | JW | 0-0 | 34-13-11 | D00101 | | DED | | | TB0241Y | | | JW | 050-099, 150-199 |
| 248Z | | | | JW | 0-0 | 34-13-11 | D00101 | | DED | | | TB0241Y | REF | | JW | 275-299 |
| 249B | 24 | | PW | JX | 7-1 | 34-13-11 | D00111 | | 34 | | | TB0241Y | C010 | BJ | | 050-099 |
| 249B | 24 | | PW | JX | 8-0 | 34-13-11 | D00111 | | 34 | | | TB0241Y | C010 | BJ | | 150-199, 275-299 |
| 249R | 24 | | PW | JX | 0-0 | 34-13-11 | D00111 | | 33 | | | TB0241Y | C009 | BJ | | ALL |
| 249Z | | | | JX | 0-0 | 34-13-11 | D00111 | | DED | | | TB0241Y | | | JW | 050-099, 150-199 |
| 249Z | | | | JX | 0-0 | 34-13-11 | D00111 | | DED | | | TB0241Y | REF | | JW | 275-299 |
| 252B | 20 | | PR | KB | 12-0 | 34-12-21 | TB0243X | A008 | BJ | | | D00299 | | 5 | | ALL |
| 252R | 20 | | PR | KB | 0-0 | 34-12-21 | TB0243X | A007 | BJ | | | D00299 | | 2 | | ALL |
| 252Z | | | | KB | 0-0 | 34-12-21 | TB0243X | B008 | BJ | | | D00299 | DED | | | ALL |
| 253B | 24 | | PW | KC | 12-0 | 34-22-81 | TB0243Y | C006 | BJ | | | D00645 | | 32 | | 050-099 |
| 253B | 24 | | PW | KC | 13-0 | 34-22-81 | TB0243Y | C006 | BJ | | | D00645 | | 32 | | 150-199, 275-299 |
| 253R | 24 | | PW | KC | 0-0 | 34-22-81 | TB0243Y | C005 | BJ | | | D00645 | | 31 | | ALL |
| 253Z | | | | KC | 0-0 | 34-22-81 | TB0243Y | | | | KC | D00645 | DED | | | ALL |
| 260B | 24 | | PL | KJ | 9-4 | 22-31-12 | D05255P | | 4 | | | D01669 | | 6 | | 050-099 |
| 260B | 24 | | PL | KJ | 10-0 | 22-31-12 | D05255P | | 4 | | | D01669 | | 6 | | 150-199, 275-299 |
| 260R | 24 | | PL | KJ | 0-0 | 22-31-12 | D05255P | | 3 | | | D01669 | | 5 | | ALL |
| 261B | 22 | | PB | KK | 9-4 | 22-31-12 | D05255P | | 6 | | | D01669 | | 4 | | 050-099 |
| 261B | 22 | | PB | KK | 10-0 | 22-31-12 | D05255P | | 6 | | | D01669 | | 4 | | 150-199, 275-299 |
| 261R | 22 | | PB | KK | 0-0 | 22-31-12 | D05255P | | 5 | | | D01669 | | 3 | | ALL |
| 262B | 24 | | PL | KL | 9-4 | 22-31-12 | D05255P | | 8 | | | D01669 | | 7 | | 050-099 |
| 262B | 24 | | PL | KL | 10-0 | 22-31-12 | D05255P | | 8 | | | D01669 | | 7 | | 150-199, 275-299 |
| 262R | 24 | | PL | KL | 0-0 | 22-31-12 | D05255P | | 7 | | | D01669 | | 8 | | ALL |
| 263B | 24 | | PW | KM | 9-4 | 22-32-11 | D05255P | | 14 | | | D01669 | | 27 | | 050-099 |
| 263B | 24 | | PW | KM | 10-0 | 22-32-11 | D05255P | | 14 | | | D01669 | | 27 | | 150-199, 275-299 |
| 263R | 24 | | PW | KM | 0-0 | 22-32-11 | D05255P | | 13 | | | D01669 | | 26 | | ALL |
| 263Z | | | | KM | 0-0 | 22-32-11 | D05255P | | 9 | | | D01669 | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 10

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | | |
| 265B | 24 | PW | KO | | 8-0 | 34-22-91 | D00647 | | 32 | | | | TB0243Y | C006 | BJ | | ALL |
| 265R | 24 | PW | KO | | 0-0 | 34-22-91 | D00647 | | 31 | | | | TB0243Y | C005 | BJ | | ALL |
| 265Z | | | KO | | 0-0 | 34-22-91 | D00647 | | DED | | | | TB0243Y | | | KC | ALL |
| 267B | 24 | PW | KQ | | 8-0 | 34-22-91 | D00647 | | 14 | | | | TB0243Y | C010 | BJ | | ALL |
| 267R | 24 | PW | KQ | | 0-0 | 34-22-91 | D00647 | | 13 | | | | TB0243Y | C009 | BJ | | ALL |
| 267Z | | | KQ | | 0-0 | 34-22-91 | D00647 | | DED | | | | TB0243Y | | | IR | ALL |
| 269B | 24 | PW | KS | | 8-0 | 34-22-91 | D00647 | | 49 | | | | TB0243Y | A010 | BJ | | ALL |
| 269R | 24 | PW | KS | | 0-0 | 34-22-91 | D00647 | | 48 | | | | TB0243Y | A009 | BJ | | ALL |
| 269Z | | | KS | | 0-0 | 34-22-91 | D00647 | | DED | | | | TB0243Y | | | IS | ALL |
| 282B | 24 | PW | LG | | 7-0 | 34-45-14 | D05255P | | 47 | | | | D00113 | 44 | | | 050-099 |
| 282B | 24 | PW | LG | | 9-0 | 34-45-14 | D05255P | | 47 | | | | D00113 | 44 | | | 150-199, 275-299 |
| 282R | 24 | PW | LG | | 0-0 | 34-45-14 | D05255P | | 46 | | | | D00113 | 25 | | | ALL |
| 282Z | | | LG | | 0-0 | 34-45-14 | D05255P | | 48 | | | | D00113 | DED | | | ALL |
| 301 | 20 | UA | | | 6-11 | 31-25-11 | GD00061 | | S.. | 2 | | | D00103 | | | MA | 050-099 |
| 301 | 20 | UA | | | 7-0 | 31-25-11 | D00103 | | | | MA | | GD00061 | S.. | 2 | | 150-199 |
| 301 | 20 | UA | | | 7-0 | 31-25-11 | D00103 | | REF | | MA | | GD00061 | S.. | 2 | | 275-299 |
| 301B | 24 | PX | MA | | 5-4 | 31-25-11 | D05014J | | 2 | | | | D00103 | 14 | | | 050-099 |
| 301B | 24 | PX | MA | | 5-11 | 31-25-11 | D00103 | | 14 | | | | D05014J | 2 | | | 150-199, 275-299 |
| 301R | 24 | PX | MA | | 0-0 | 31-25-11 | D05014J | | 1 | | | | D00103 | 13 | | | 050-099 |
| 301R | 24 | PX | MA | | 0-0 | 31-25-11 | D00103 | | 13 | | | | D05014J | 1 | | | 150-199, 275-299 |
| 301Y | 24 | PX | MA | | 0-0 | 31-25-11 | D05014J | | 3 | | | | D00103 | 15 | | | 050-099 |
| 301Y | 24 | PX | MA | | 0-0 | 31-25-11 | D00103 | | 15 | | | | D05014J | 3 | | | 150-199, 275-299 |
| 301Z | | | MA | | 0-0 | 31-25-11 | D05014J | | 14 | | | | D00103 | | | MA | 050-099 |
| 301Z | | | MA | | 0-0 | 31-25-11 | D00103 | | | | MA | | D05014J | 14 | | | 150-199 |
| 301Z | | | MA | | 0-0 | 31-25-11 | D00103 | | REF | | MA | | D05014J | 14 | | | 275-299 |
| 302B | 24 | PM | MB | | 7-2 | 34-12-11 | D04167P | | 19 | | | | D00111 | 20 | | | 050-099 |
| 302B | 24 | PM | MB | | 9-0 | 34-12-11 | D04167P | | 19 | | | | D00111 | 20 | | | 150-199, 275-299 |
| 302R | 24 | PM | MB | | 0-0 | 34-12-11 | D04167P | | 18 | | | | D00111 | 19 | | | ALL |
| 302Y | 24 | PM | MB | | 0-0 | 34-12-11 | D04167P | | 20 | | | | D00111 | 21 | | | ALL |
| 308B | 24 | PM | MH | | 7-1 | 34-12-21 | D00111 | | 25 | | | | D04147P | 32 | | | 050-099 |
| 308B | 24 | PM | MH | | 9-0 | 34-12-21 | D00111 | | 25 | | | | D04147P | 32 | | | 150-199, 275-299 |
| 308R | 24 | PM | MH | | 0-0 | 34-12-21 | D00111 | | 24 | | | | D04147P | 31 | | | ALL |
| 308Y | 24 | PM | MH | | 0-0 | 34-12-21 | D00111 | | 26 | | | | D04147P | 33 | | | ALL |
| 350B | 24 | PM | NY | | 2-2 | 31-41-14 | D05115P | | 13 | | | | D05111P | 12 | | | 050-099 |
| 350B | 24 | PM | NY | | 3-0 | 31-41-14 | D05115P | | 13 | | | | D05111P | 12 | | | 150-199, 275-299 |
| 350R | 24 | PM | NY | | 0-0 | 31-41-14 | D05115P | | 12 | | | | D05111P | 11 | | | ALL |
| 350Y | 24 | PM | NY | | 0-0 | 31-41-14 | D05115P | | 14 | | | | D05111P | 13 | | | ALL |
| 351B | 24 | PX | OA | | 9-5 | 23-51-12 | D00157 | | 25 | | | | D05415P | 18 | | | 050-099 |
| 351B | 24 | PX | OA | | 10-0 | 23-51-12 | D00157 | | 25 | | | | D05415P | 18 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 11

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 351R | 24 | PX | OA | | 0-0 | 23-51-12 | D00157 | | 24 | | | D05415P | 17 | | ALL |
| 351Y | 24 | PX | OA | | 0-0 | 23-51-12 | D00157 | | 12 | | | D05415P | 19 | | ALL |
| 351Z | | | OA | | 0-0 | 23-51-12 | D00157 | | DED | | | D05415P | 20 | | ALL |
| 501B | 24 | PW | UA | | 2-2 | 31-41-12 | D05115P | | 2 | | | D05111P | 3 | | 050-099 |
| 501B | 24 | PW | UA | | 3-0 | 31-41-12 | D05115P | | 2 | | | D05111P | 3 | | 150-199, 275-299 |
| 501R | 24 | PW | UA | | 0-0 | 31-41-12 | D05115P | | 1 | | | D05111P | 2 | | ALL |
| 501Z | | | UA | | 0-0 | 31-41-12 | D05115P | | 3 | | | D05111P | 4 | | ALL |
| 502B | 24 | PL | UB | | 4-1 | 31-41-14 | TB0241Y | A004 | BJ | | | D05111P | 6 | | 050-099 |
| 502B | 24 | PL | UB | | 5-0 | 31-41-14 | TB0241Y | A004 | BJ | | | D05111P | 6 | | 150-199, 275-299 |
| 502R | 24 | PL | UB | | 0-0 | 31-41-14 | TB0241Y | A003 | BJ | | | D05111P | 5 | | ALL |
| 504B | 24 | PL | UD | | 4-1 | 31-41-14 | TB0241X | A005 | BJ | | | D05111P | 8 | | 050-099 |
| 504B | 24 | PL | UD | | 5-0 | 31-41-14 | TB0241X | A005 | BJ | | | D05111P | 8 | | 150-199, 275-299 |
| 504R | 24 | PL | UD | | 0-0 | 31-41-14 | TB0241X | A006 | BJ | | | D05111P | 7 | | ALL |
| 505B | 24 | PL | UE | | 4-1 | 31-41-14 | TB0241X | B005 | BJ | | | D05111P | 10 | | 050-099 |
| 505B | 24 | PL | UE | | 5-0 | 31-41-14 | TB0241X | B005 | BJ | | | D05111P | 10 | | 150-199, 275-299 |
| 505R | 24 | PL | UE | | 0-0 | 31-41-14 | TB0241X | B006 | BJ | | | D05111P | 9 | | ALL |
| 507B | 24 | PL | UG | | 4-1 | 34-22-15 | D05809P | | 3 | | | TB0241Y | A004 | BJ | 050-099 |
| 507B | 24 | PL | UG | | 5-0 | 34-22-15 | D05809P | | 3 | | | TB0241Y | A004 | BJ | 150-199, 275-299 |
| 507R | 24 | PL | UG | | 0-0 | 34-22-15 | D05809P | | 2 | | | TB0241Y | A003 | BJ | ALL |
| 509B | 24 | PW | UI | | 10-6 | 73-21-14 | D10122 | | 16 | | | D06186P | 21 | | 050-099 |
| 509B | 24 | PW | UI | | 12-0 | 73-21-14 | D10122 | | 16 | | | D06186P | 21 | | 150-199, 275-299 |
| 509R | 24 | PW | UI | | 0-0 | 73-21-14 | D10122 | | 15 | | | D06186P | 22 | | ALL |
| 509Z | | | UI | | 0-0 | 73-21-14 | D10122 | | | | UI | D06186P | 25 | | 050-099 |
| 509Z | | | UI | | 0-0 | 73-21-14 | D10122 | REF | | | UJ | D06186P | 25 | | 150-199, 275-299 |
| 510B | 24 | PW | UJ | | 10-6 | 73-21-14 | D06184P | | 11 | | | D10122 | 24 | | 050-099 |
| 510B | 24 | PW | UJ | | 12-0 | 73-21-14 | D06184P | | 11 | | | D10122 | 24 | | 150-199, 275-299 |
| 510R | 24 | PW | UJ | | 0-0 | 73-21-14 | D06184P | | 12 | | | D10122 | 23 | | ALL |
| 510Z | | | UJ | | 0-0 | 73-21-14 | D06184P | | 13 | | | D10122 | | | UI |
| 510Z | | | UJ | | 0-0 | 73-21-14 | D06184P | | 13 | | | D10122 | REF | | UJ |
| 512 | 20 | UA | | | 1-6 | 22-12-11 | D00475 | | | | UL | GD00313 | S.. | 2 | 050-099 |
| 512 | 20 | UA | | | 3-0 | 22-12-11 | D00475 | | | | UL | GD00313 | S.. | 2 | 150-199, 275-299 |
| 512B | 24 | PW | UL | | 8-10 | 22-12-11 | D00475 | | 21 | | | D05419P | 5 | | 050-099 |
| 512B | 24 | PW | UL | | 9-0 | 22-12-11 | D00475 | | 21 | | | D05419P | 5 | | 150-199, 275-299 |
| 512R | 24 | PW | UL | | 0-0 | 22-12-11 | D00475 | | 20 | | | D05419P | 4 | | ALL |
| 512Z | | | UL | | 0-0 | 22-12-11 | D00475 | | | | UL | D05419P | 6 | | ALL |
| 513 | 20 | UA | | | 1-6 | 22-13-11 | D00475 | | | | UM | GD00313 | S.. | 2 | 050-099 |
| 513 | 20 | UA | | | 3-0 | 22-13-11 | D00475 | | | | UM | GD00313 | S.. | 2 | 150-199, 275-299 |
| 513B | 24 | PW | UM | | 8-10 | 22-13-11 | D00475 | | 29 | | | D05419P | 8 | | 050-099 |
| 513B | 24 | PW | UM | | 9-0 | 22-13-11 | D00475 | | 29 | | | D05419P | 8 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11
 Section W0010
 Page 12
 May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | |
| 513R | 24 | PW | UM | 0-0 | 22-13-11 | D00475 | | 28 | | | | | D05419P | 7 | | ALL |
| 513Z | | | UM | 0-0 | 22-13-11 | D00475 | | | | UM | | | D05419P | 9 | | ALL |
| 514 | 20 | UA | | 1-6 | 22-14-11 | D00475 | | | | UN | | | GD00313 | S.. | 2 | 050-099 |
| 514B | 20 | UA | | 3-0 | 22-14-11 | D00475 | | | | UN | | | GD00313 | S.. | 2 | 150-199, 275-299 |
| 514B | 24 | PW | UN | 8-10 | 22-14-11 | D00475 | | 23 | | | | | D05419P | 11 | | 050-099 |
| 514B | 24 | PW | UN | 9-0 | 22-14-11 | D00475 | | 23 | | | | | D05419P | 11 | | 150-199, 275-299 |
| 514R | 24 | PW | UN | 0-0 | 22-14-11 | D00475 | | 24 | | | | | D05419P | 10 | | ALL |
| 514Z | | | UN | 0-0 | 22-14-11 | D00475 | | | | UN | | | D05419P | 12 | | ALL |
| 515 | 20 | UA | | 1-6 | 22-12-31 | D00479 | | | | UO | | | GD00313 | S.. | 2 | ALL |
| 515B | 24 | PW | UO | 8-8 | 22-12-31 | D00479 | | 21 | | | | | D04501P | 4 | | 050-099 |
| 515B | 24 | PW | UO | 9-0 | 22-12-31 | D00479 | | 21 | | | | | D04501P | 4 | | 150-199, 275-299 |
| 515R | 24 | PW | UO | 0-0 | 22-12-31 | D00479 | | 20 | | | | | D04501P | 3 | | ALL |
| 515Z | | | UO | 0-0 | 22-12-31 | D00479 | | | | UO | | | D04501P | 5 | | ALL |
| 516B | 24 | PW | UP | 9-5 | 34-55-11 | D00157 | | 29 | | | | | D05415P | 3 | | 050-099 |
| 516B | 24 | PW | UP | 10-0 | 34-55-11 | D00157 | | 29 | | | | | D05415P | 3 | | 150-199, 275-299 |
| 516R | 24 | PW | UP | 0-0 | 34-55-11 | D00157 | | 16 | | | | | D05415P | 2 | | ALL |
| 516Z | | | UP | 0-0 | 34-55-11 | D00157 | | 28 | | | | | D05415P | 4 | | ALL |
| 517B | 24 | PW | UQ | 9-5 | 34-51-11 | D00157 | | 21 | | | | | D05415P | 7 | | 050-099 |
| 517B | 24 | PW | UQ | 10-0 | 34-51-11 | D00157 | | 21 | | | | | D05415P | 7 | | 150-199, 275-299 |
| 517R | 24 | PW | UQ | 0-0 | 34-51-11 | D00157 | | 8 | | | | | D05415P | 6 | | ALL |
| 517Z | | | UQ | 0-0 | 34-51-11 | D00157 | | 20 | | | | | D05415P | 8 | | ALL |
| 518B | 24 | PW | UR | 9-5 | 34-51-11 | D00157 | | 31 | | | | | D05415P | 10 | | 050-099 |
| 518B | 24 | PW | UR | 10-0 | 34-51-11 | D00157 | | 31 | | | | | D05415P | 10 | | 150-199, 275-299 |
| 518R | 24 | PW | UR | 0-0 | 34-51-11 | D00157 | | 18 | | | | | D05415P | 9 | | ALL |
| 518Z | | | UR | 0-0 | 34-51-11 | D00157 | | 30 | | | | | D05415P | 11 | | ALL |
| 519B | 24 | PW | US | 9-5 | 34-51-11 | D00157 | | 22 | | | | | D05415P | 15 | | 050-099 |
| 519B | 24 | PW | US | 10-0 | 34-51-11 | D00157 | | 22 | | | | | D05415P | 15 | | 150-199, 275-299 |
| 519R | 24 | PW | US | 0-0 | 34-51-11 | D00157 | | 10 | | | | | D05415P | 14 | | ALL |
| 519Z | | | US | 0-0 | 34-51-11 | D00157 | | 23 | | | | | D05415P | 16 | | ALL |
| 520B | 22 | PB | UT | 9-5 | 34-51-11 | D00157 | | 2 | | | | | D05415P | 13 | | 050-099 |
| 520B | 22 | PB | UT | 10-0 | 34-51-11 | D00157 | | 2 | | | | | D05415P | 13 | | 150-199, 275-299 |
| 520R | 22 | PB | UT | 0-0 | 34-51-11 | D00157 | | 1 | | | | | D05415P | 12 | | ALL |
| 602 | 24 | PK | | 6-11 | 31-51-43 | D04285P | | 18 | | | | | D05255P | 18 | | 050-099 |
| 602 | 24 | PK | | 8-0 | 31-51-43 | D04285P | | 18 | | | | | D05255P | 18 | | 150-199, 275-299 |
| 603 | 20 | PA | | 7-5 | 22-31-12 | GD03700 | | S.. | 2 | | | | D01669 | 31 | | 050-099 |
| 603 | 20 | PA | | 8-0 | 22-31-12 | GD03700 | | S.. | 2 | | | | D01669 | 31 | | 150-199, 275-299 |
| 609 | 20 | PA | | 5-0 | 34-22-81 | D05043P | | 2 | | | | | GD00079 | D.. | 2 | ALL |
| 610 | 24 | PV | YI | 11-0 | 34-22-81 | D00647 | | 29 | | | | | TB0241Y | A013 | BJ | ALL |
| 610Z | | | YI | 0-0 | 34-22-81 | D00647 | | DED | | | | | TB0241Y | DED | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 13

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 611 | 24 | PV | | YJ | 8-0 | 34-22-91 | D00647 | | 54 | | TB0243X | B003 | BJ | | ALL |
| 611Z | | | | YJ | 0-0 | 34-22-91 | D00647 | | DED | | TB0243X | DED | | | ALL |
| 612 | 20 | PA | | | 7-0 | 34-22-91 | D00647 | | 55 | | GD00071 | A.. | 2 | | ALL |
| 613 | 20 | PA | | | 7-0 | 34-22-91 | D00647 | | 3 | | GD00079 | D.. | 2 | | ALL |
| 614 | 20 | PA | | | 7-0 | 34-22-91 | D00647 | | 6 | | GD00077 | S.. | 2 | | ALL |
| 615 | 20 | PA | | | 7-0 | 34-22-91 | D00647 | | 28 | | GD00077 | S.. | 2 | | ALL |
| 616 | 24 | PK | | | 6-11 | 34-12-12 | D04285P | | 29 | | D05255P | | 37 | | 050-099 |
| 616 | 24 | PK | | | 8-0 | 34-12-12 | D04285P | | 29 | | D05255P | | 37 | | 150-199, 275-299 |
| 622 | 22 | PA | | | 6-11 | 34-61-15 | D04285P | | 30 | | D05255P | | 38 | | 050-099 |
| 622 | 22 | PA | | | 8-0 | 34-61-15 | D04285P | | 30 | | D05255P | | 38 | | 150-199, 275-299 |
| 623 | 24 | PK | | | 10-1 | 31-51-31 | D05305P | | 1 | | D05419P | | 16 | | 050-099 |
| 623 | 24 | PK | | | 10-0 | 31-51-31 | D05305P | | 1 | | D05419P | | 16 | | 150-199, 275-299 |
| 624 | 20 | PA | | | 8-0 | 31-51-31 | D05305P | | 2 | | GD00079 | D.. | 2 | | ALL |
| 625 | 24 | PK | | | 6-11 | 31-51-42 | D04285P | | 31 | | D05255P | | 27 | | 050-099 |
| 625 | 24 | PK | | | 7-0 | 31-51-42 | D04285P | | 31 | | D05255P | | 27 | | 150-199, 275-299 |
| 626 | 24 | PK | | | 6-11 | 34-16-11 | D04285P | | 32 | | D05255P | | 32 | | 050-099 |
| 626 | 24 | PK | | | 7-0 | 34-16-11 | D04285P | | 32 | | D05255P | | 32 | | 150-199, 275-299 |
| 627 | 22 | PA | | | 6-11 | 34-46-11 | D04285P | | 33 | | D05255P | | 20 | | 050-099 |
| 627 | 22 | PA | | | 7-0 | 34-46-11 | D04285P | | 33 | | D05255P | | 20 | | 150-199, 275-299 |
| 628 | 22 | PA | | | 6-11 | 34-46-11 | D04285P | | 34 | | D05255P | | 21 | | 050-099 |
| 628 | 22 | PA | | | 7-0 | 34-46-11 | D04285P | | 34 | | D05255P | | 21 | | 150-199, 275-299 |
| 629 | 24 | PK | | | 6-11 | 34-46-11 | D04285P | | 35 | | D05255P | | 22 | | 050-099 |
| 629 | 24 | PK | | | 7-0 | 34-46-11 | D04285P | | 35 | | D05255P | | 22 | | 150-199, 275-299 |
| 630 | 20 | PA | | | 4-6 | 34-46-11 | D04285P | | 36 | | GD03700 | D.. | 2 | | 050-099 |
| 630 | 20 | PA | | | 5-0 | 34-46-11 | D04285P | | 36 | | GD03700 | D.. | 2 | | 150-199, 275-299 |
| 631 | 24 | PK | | | 9-7 | 34-46-12 | D05305P | | 3 | | D04171P | | 13 | | 050-099 |
| 631 | 24 | PK | | | 10-0 | 34-46-12 | D05305P | | 3 | | D04171P | | 13 | | 150-199, 275-299 |
| 632 | 20 | PA | | | 8-4 | 34-46-12 | D05305P | | 4 | | GD00059 | D.. | 2 | | 050-099 |
| 632 | 20 | PA | | | 8-0 | 34-46-12 | D05305P | | 4 | | GD00059 | D.. | 2 | | 150-199, 275-299 |
| 633 | 24 | PK | | | 9-7 | 34-46-12 | D05305P | | 5 | | D04171P | | 15 | | 050-099 |
| 633 | 24 | PK | | | 10-0 | 34-46-12 | D05305P | | 5 | | D04171P | | 15 | | 150-199, 275-299 |
| 634 | 20 | PA | | | 8-4 | 34-46-12 | D05305P | | 6 | | GD00059 | D.. | 2 | | 050-099 |
| 634 | 20 | PA | | | 8-0 | 34-46-12 | D05305P | | 6 | | GD00059 | D.. | 2 | | 150-199, 275-299 |
| 650 | 22 | PA | | | 3-11 | 31-41-11 | D04163P | | 2 | | D05111P | | 1 | | ALL |
| 651 | 20 | PA | | | 6-3 | 31-41-12 | D04285P | | 25 | | GD00057 | D.. | 2 | | 050-099 |
| 651 | 20 | PA | | | 7-0 | 31-41-12 | D04285P | | 25 | | GD00057 | D.. | 2 | | 150-199, 275-299 |
| 652 | 22 | PA | | | 7-0 | 31-41-12 | D04285P | | 26 | | D05115P | | 4 | | 050-099 |
| 652 | 22 | PA | | | 8-0 | 31-41-12 | D04285P | | 26 | | D05115P | | 4 | | 150-199, 275-299 |
| 653 | 22 | PA | | | 7-0 | 31-41-12 | D04285P | | 27 | | D05115P | | 5 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 14

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | |
| 653 | 22 | | PA | | 8-0 | 31-41-12 | D04285P | | 27 | | | D05115P | | 5 | | 150-199, 275-299 |
| 654 | 24 | | PK | | 4-9 | 31-41-16 | D05014J | | 4 | | | TB0241Y | C003 | BJ | | 050-099 |
| 654 | 24 | | PK | | 6-0 | 31-41-16 | D05014J | | 4 | | | TB0241Y | C003 | BJ | | 150-199, 275-299 |
| 655 | 24 | | PK | | 4-9 | 31-41-16 | D05014J | | 5 | | | TB0241Y | C004 | BJ | | 050-099 |
| 655 | 24 | | PK | | 6-0 | 31-41-16 | D05014J | | 5 | | | TB0241Y | C004 | BJ | | 150-199, 275-299 |
| 658 | 24 | | PK | | 4-1 | 31-41-16 | D05111P | | 14 | | | TB0241Y | C003 | BJ | | 050-099 |
| 658 | 24 | | PK | | 5-0 | 31-41-16 | D05111P | | 14 | | | TB0241Y | C003 | BJ | | 150-199, 275-299 |
| 659 | 24 | | PK | | 4-1 | 31-41-16 | D05111P | | 15 | | | TB0241Y | C004 | BJ | | 050-099 |
| 659 | 24 | | PK | | 5-0 | 31-41-16 | D05111P | | 15 | | | TB0241Y | C004 | BJ | | 150-199, 275-299 |
| 660 | 22 | | PA | | 2-2 | 31-41-17 | D05111P | | 16 | | | D05115P | | 17 | | 050-099 |
| 660 | 22 | | PA | | 3-0 | 31-41-17 | D05111P | | 16 | | | D05115P | | 17 | | 150-199, 275-299 |
| 661 | 22 | | PA | | 2-2 | 31-41-17 | D05111P | | 17 | | | D05115P | | 18 | | 050-099 |
| 661 | 22 | | PA | | 3-0 | 31-41-17 | D05111P | | 17 | | | D05115P | | 18 | | 150-199, 275-299 |
| 662 | 24 | | PK | | 9-0 | 32-71-11 | D05305P | | 32 | | | D06186P | | 32 | | 150-199, 275-299 |
| 664 | 16 | | PA | | 6-1 | 33-13-11 | D10122 | | 1 | FM | | SP00345 | | 9 | | 050-099 |
| 664 | 16 | | PA | | 7-0 | 33-13-11 | D10122 | | 1 | FM | | SP00345 | | 9 | | 150-199, 275-299 |
| 665 | 16 | | PA | | 6-1 | 33-13-11 | D10122 | | 2 | FM | | GD03698 | A.. | 2 | | 050-099 |
| 665 | 16 | | PA | | 7-0 | 33-13-11 | D10122 | | 2 | FM | | GD03698 | A.. | 2 | | 150-199, 275-299 |
| 666 | 20 | | PA | | 7-6 | 33-13-13 | D00240 | | 1 | | | SP00347 | | 9 | | 050-099 |
| 666 | 20 | | PA | | 8-0 | 33-13-13 | D00240 | | 1 | | | SP00347 | | 9 | | 150-199, 275-299 |
| 667 | 18 | | PA | | 7-5 | 33-13-13 | D01669 | | 1 | DK | | SP00347 | | 9 | | 050-099 |
| 667 | 18 | | PA | | 8-0 | 33-13-13 | D01669 | | 1 | DK | | SP00347 | | 9 | | 150-199, 275-299 |
| 669 | 18 | | PA | | 7-3 | 33-13-13 | D05305P | | 9 | DK | | SP00347 | | 9 | | 050-099 |
| 669 | 18 | | PA | | 6-0 | 33-13-13 | D05305P | | 9 | DK | | SP00347 | | 9 | | 150-199, 275-299 |
| 670 | 20 | | PA | | 6-8 | 33-13-13 | D00240 | | 2 | | | GD03096 | A.. | 2 | | 050-099 |
| 670 | 20 | | PA | | 7-0 | 33-13-13 | D00240 | | 2 | | | GD03096 | A.. | 2 | | 150-199, 275-299 |
| 671 | 18 | | PA | | 6-7 | 33-13-13 | D01669 | | 2 | DK | | GD03096 | A.. | 2 | | 050-099 |
| 671 | 18 | | PA | | 7-0 | 33-13-13 | D01669 | | 2 | DK | | GD03096 | A.. | 2 | | 150-199, 275-299 |
| 672 | 18 | | PA | | 6-5 | 33-13-13 | D05305P | | 10 | DK | | GD03096 | A.. | 2 | | 050-099 |
| 672 | 18 | | PA | | 7-0 | 33-13-13 | D05305P | | 10 | DK | | GD03096 | A.. | 2 | | 150-199, 275-299 |
| 682 | 18 | | PA | | 6-5 | 33-13-13 | D05305P | | 12 | DK | | GD03096 | A.. | 2 | | 050-099 |
| 682 | 18 | | PA | | 7-0 | 33-13-13 | D05305P | | 12 | DK | | GD03096 | A.. | 2 | | 150-199, 275-299 |
| 699 | 24 | | PK | | 6-11 | 34-46-11 | D05255P | | 23 | | | D04285P | | 23 | | 050-099 |
| 699 | 24 | | PK | | 7-0 | 34-46-11 | D04285P | | 23 | | | D05255P | | 23 | | 150-199, 275-299 |
| 701 | 24 | | PK | | 0-7 | 22-14-11 | D01363 | | 15 | | | D01363 | | 4 | | 050-099 |
| 701 | 24 | | PK | | 1-0 | 22-14-11 | D01363 | | 15 | | | D01363 | | 4 | | 150-199, 275-299 |
| 702 | 24 | | PK | | 4-4 | 22-14-11 | D00633 | | 9 | | | SM00043 | | W | | ALL |
| 703 | 24 | | PK | | 4-4 | 22-14-11 | D00633 | | 8 | | | SM00043 | | W | | ALL |
| 704 | 24 | | PK | | 4-4 | 22-14-11 | D00633 | | 2 | | | SM00043 | | W | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 15

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 708 | 22 | PQ | G8 | | 11-5 | 33-16-15 | D05043P | | 10 | | TB0245Z | 5 | BJ | | 050-099 |
| 708 | 22 | PQ | G8 | | 11-0 | 33-16-15 | D05043P | | 10 | | TB0245Z | 5 | BJ | | 150-199, 275-299 |
| 708Z | | | G8 | | 0-0 | 33-16-15 | D05043P | | DED | | TB0245Z | DED | | | ALL |
| 709 | 22 | PQ | G9 | | 6-0 | 33-16-15 | D05043P | | 11 | | TB0243Y | C001 | BJ | | 050-099 |
| 709 | 22 | PQ | H5 | | 6-0 | 33-16-15 | TB0243Y | | C001 | BJ | D05043P | 11 | | | 150-199, 275-299 |
| 709Z | | | G9 | | 0-0 | 33-16-15 | D05043P | | DED | | TB0243Y | DED | | | 050-099 |
| 709Z | | | H5 | | 0-0 | 33-16-15 | TB0243Y | | DED | | D05043P | DED | | | 150-199, 275-299 |
| 713 | 22 | PA | | | 9-0 | 33-16-15 | TB0243Y | | A016 | BJ | D05305P | 15 | | | ALL |
| 716 | 20 | PA | | | 4-11 | 33-13-11 | D00103 | | 1 | | SP00345 | | 9 | | ALL |
| 717 | 22 | PA | | | 9-0 | 33-16-15 | D05305P | | 16 | | TB0247Z | 9 | BJ | | ALL |
| 718 | 22 | PQ | H8 | | 10-0 | 33-16-13 | D04285P | | 4 | | TB0243Y | C001 | BJ | | 050-099 |
| 718 | 22 | PQ | DH | | 10-0 | 33-16-13 | D04285P | | 4 | | TB0243Y | C001 | BJ | | 150-199, 275-299 |
| 718Z | | | H8 | | 0-0 | 33-16-13 | D04285P | | DED | | TB0243Y | DED | | | 050-099 |
| 718Z | | | DH | | 0-0 | 33-16-13 | D04285P | | DED | | TB0243Y | DED | | | 150-199, 275-299 |
| 720 | 22 | PA | | | 3-8 | 34-22-81 | D04167P | | 30 | | TB0241Y | A010 | BJ | | 050-099 |
| 720 | 22 | PA | | | 5-0 | 34-22-81 | D04167P | | 30 | | TB0241Y | A010 | BJ | | 150-199, 275-299 |
| 722 | 22 | PA | | | 10-1 | 21-33-11 | D04285P | | 40 | | D04560P | 12 | | | 050-099 |
| 722 | 22 | PA | | | 11-0 | 21-33-11 | D04285P | | 40 | | D04560P | 12 | | | 150-199, 275-299 |
| 723 | 18 | PA | | | 8-8 | 32-35-11 | D05305P | | 21 | DK | D06184P | 1 | DL | | 050-099 |
| 723 | 18 | PA | | | 9-0 | 32-35-11 | D05305P | | 21 | DK | D06184P | 1 | DL | | 150-199, 275-299 |
| 728 | 22 | PA | | | 8-8 | 32-46-11 | D05305P | | 26 | | D06186P | 1 | | | 050-099 |
| 728 | 22 | PA | | | 9-0 | 32-46-11 | D05305P | | 26 | | D06186P | 1 | | | 150-199, 275-299 |
| 729 | 24 | PK | | | 8-8 | 32-61-14 | D05305P | | 27 | | D06186P | 2 | | | 050-099 |
| 729 | 24 | PK | | | 9-0 | 32-61-14 | D05305P | | 27 | | D06186P | 2 | | | 150-199, 275-299 |
| 730 | 24 | PK | | | 8-8 | 32-61-14 | D05305P | | 28 | | D06186P | 3 | | | 050-099 |
| 730 | 24 | PK | | | 9-0 | 32-61-14 | D05305P | | 28 | | D06186P | 3 | | | 150-199, 275-299 |
| 731 | 24 | PK | | | 8-8 | 32-61-14 | D05305P | | 29 | | D06186P | 4 | | | 050-099 |
| 731 | 24 | PK | | | 9-0 | 32-61-14 | D05305P | | 29 | | D06186P | 4 | | | 150-199, 275-299 |
| 732 | 24 | PK | | | 8-8 | 32-61-14 | D05305P | | 30 | | D06186P | 5 | | | 050-099 |
| 732 | 24 | PK | | | 9-0 | 32-61-14 | D05305P | | 30 | | D06186P | 5 | | | 150-199, 275-299 |
| 733 | 24 | PK | | | 8-8 | 32-61-14 | D05305P | | 31 | | D06186P | 6 | | | 050-099 |
| 733 | 24 | PK | | | 9-0 | 32-61-14 | D05305P | | 31 | | D06186P | 6 | | | 150-199, 275-299 |
| 736 | 24 | PV | J6 | | 12-0 | 73-21-14 | TB0247X | | A006 | BJ | D10122 | 3 | | | 050-099 |
| 736 | 24 | PV | J6 | | 11-0 | 73-21-14 | TB0247X | | A006 | BJ | D10122 | 3 | | | 150-199, 275-299 |
| 736Z | | | J6 | | 0-0 | 73-21-14 | TB0247X | | DED | | D10122 | DED | | | ALL |
| 737 | 20 | PA | | | 6-1 | 73-21-14 | D10122 | | 21 | | GD03702 | D.. | 2 | | 050-099 |
| 737 | 20 | PA | | | 7-0 | 73-21-14 | D10122 | | 21 | | GD03702 | D.. | 2 | | 150-199, 275-299 |
| 738 | 24 | PK | | | 10-6 | 73-21-14 | D10122 | | 18 | | D06186P | 20 | | | 050-099 |
| 738 | 24 | PK | | | 12-0 | 73-21-14 | D10122 | | 18 | | D06186P | 20 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 16

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 739 | 22 | | PA | | 9-9 | 79-33-11 | D04285P | | | | | | | | 050-099 |
| 739 | 22 | | PA | | 10-0 | 79-33-11 | D04285P | | | | | | | | 150-199, 275-299 |
| 740 | 20 | | PA | | 7-3 | 27-51-11 | D05305P | | | | | | D.. | 2 | 050-099 |
| 740 | 20 | | PA | | 7-0 | 27-51-11 | D05305P | | | | | | D.. | 2 | 150-199, 275-299 |
| 741 | 24 | | PK | | 8-8 | 27-51-11 | D05305P | | | | | | | | 050-099 |
| 741 | 24 | | PK | | 9-0 | 27-51-11 | D05305P | | | | | | | | 150-199, 275-299 |
| 742 | 24 | | PK | | 8-11 | 27-58-11 | D00240 | | | | | | | | 050-099 |
| 742 | 24 | | PK | | 9-0 | 27-58-11 | D00240 | | | | | | | | 150-199, 275-299 |
| 743 | 24 | | PK | | 8-11 | 27-58-11 | D00240 | | | | | | | | 050-099 |
| 743 | 24 | | PK | | 9-0 | 27-58-11 | D00240 | | | | | | | | 150-199, 275-299 |
| 744 | 24 | | PK | | 8-11 | 27-58-11 | D00240 | | | | | | | | 050-099 |
| 744 | 24 | | PK | | 9-0 | 27-58-11 | D00240 | | | | | | | | 150-199, 275-299 |
| 745 | 24 | | PK | | 8-11 | 27-58-11 | D00240 | | | | | | | | 050-099 |
| 745 | 24 | | PK | | 9-0 | 27-58-11 | D00240 | | | | | | | | 150-199, 275-299 |
| 746 | 20 | | PA | | 7-6 | 27-58-11 | D00240 | | | | | | A.. | 2 | 050-099 |
| 746 | 20 | | PA | | 8-0 | 27-58-11 | D00240 | | | | | | A.. | 2 | 150-199, 275-299 |
| 747 | 24 | | PK | | 8-11 | 27-58-11 | D00240 | | | | | | | | 050-099 |
| 747 | 24 | | PK | | 9-0 | 27-58-11 | D00240 | | | | | | | | 150-199, 275-299 |
| 748 | 20 | | PA | | 7-6 | 27-58-11 | D00240 | | | | | | S.. | 2 | 050-099 |
| 748 | 20 | | PA | | 8-0 | 27-58-11 | D00240 | | | | | | S.. | 2 | 150-199, 275-299 |
| 749 | 24 | | PK | | 8-11 | 27-58-11 | D00240 | | | | | | | | 050-099 |
| 749 | 24 | | PK | | 9-0 | 27-58-11 | D00240 | | | | | | | | 150-199, 275-299 |
| 750 | 20 | | PA | | 7-6 | 27-58-11 | D00240 | | | | | | A.. | 2 | 050-099 |
| 750 | 20 | | PA | | 8-0 | 27-58-11 | D00240 | | | | | | A.. | 2 | 150-199, 275-299 |
| 751 | 22 | | PA | | 8-8 | 27-58-31 | D05305P | | | | | | | | 050-099 |
| 751 | 22 | | PA | | 9-0 | 27-58-31 | D05305P | | | | | | | | 150-199, 275-299 |
| 752 | 22 | | PA | | 8-8 | 27-88-11 | D05305P | | | | | | | | 050-099 |
| 752 | 22 | | PA | | 9-0 | 27-88-11 | D05305P | | | | | | | | 150-199, 275-299 |
| 754 | 22 | | PA | | 5-0 | 34-22-81 | D00645 | | | | | | A010 | BJ | 050-099 |
| 754 | 22 | | PA | | 6-0 | 34-22-81 | D00645 | | | | | | A010 | BJ | 150-199, 275-299 |
| 759 | 24 | | PK | | 10-0 | 33-16-11 | D04285P | | | | | | | | 050-099 |
| 759 | 24 | | PK | | 11-0 | 33-16-11 | D04285P | | | | | | | | 150-199, 275-299 |
| 760 | 24 | | PK | | 10-0 | 33-16-11 | D04285P | | | | | | | | 050-099 |
| 760 | 24 | | PK | | 11-0 | 33-16-11 | D04285P | | | | | | | | 150-199, 275-299 |
| 761 | 20 | | PA | | 4-6 | 33-16-11 | D04285P | | | | | | D.. | 2 | 050-099 |
| 761 | 20 | | PA | | 6-0 | 33-16-11 | D04285P | | | | | | D.. | 2 | 150-199, 275-299 |
| 762 | 22 | | PA | | 8-10 | 22-11-12 | D00475 | | | | | | | | 050-099 |
| 762 | 22 | | PA | | 9-0 | 22-11-12 | D00475 | | | | | | | | 150-199, 275-299 |
| 763 | 22 | | PA | | 8-10 | 22-11-12 | D00475 | | | | | | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 17

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 763 | 22 | | PA | | 9-0 | 22-11-12 | D00475 | | 7 | | D05419P | | 2 | | 150-199, 275-299 |
| 764 | 22 | | PA | | 8-10 | 22-11-12 | D00475 | | 30 | | D05419P | | 3 | | 050-099 |
| 764 | 22 | | PA | | 9-0 | 22-11-12 | D00475 | | 30 | | D05419P | | 3 | | 150-199, 275-299 |
| 765 | 20 | | PA | | 1-11 | 22-11-12 | D00475 | | 18 | | GD00313 | D.. | 2 | | 050-099 |
| 765 | 20 | | PA | | 3-0 | 22-11-12 | D00475 | | 18 | | GD00313 | D.. | 2 | | 150-199, 275-299 |
| 766 | 20 | | PA | | 1-11 | 22-11-12 | D00475 | | 19 | | GD00313 | S.. | 2 | | 050-099 |
| 766 | 20 | | PA | | 3-0 | 22-11-12 | D00475 | | 19 | | GD00313 | S.. | 2 | | 150-199, 275-299 |
| 767 | 24 | | PK | | 8-10 | 22-32-15 | D00475 | | 8 | | D05419P | | 13 | | 050-099 |
| 767 | 24 | | PK | | 9-0 | 22-32-15 | D00475 | | 8 | | D05419P | | 13 | | 150-199, 275-299 |
| 768 | 24 | | PK | | 8-10 | 22-32-15 | D00475 | | 25 | | D05419P | | 14 | | 050-099 |
| 768 | 24 | | PK | | 9-0 | 22-32-15 | D00475 | | 25 | | D05419P | | 14 | | 150-199, 275-299 |
| 769 | 22 | | PQ | M9 | 8-8 | 22-11-32 | D00479 | | 7 | | D04501P | | 1 | | 050-099 |
| 769 | 22 | | PQ | M9 | 9-0 | 22-11-32 | D00479 | | 7 | | D04501P | | 1 | | 150-199, 275-299 |
| 769Z | | | | M9 | 0-0 | 22-11-32 | D00479 | | DED | | D04501P | DED | | | ALL |
| 770 | 22 | | PQ | N+ | 8-8 | 22-11-32 | D00479 | | 30 | | D04501P | | 2 | | 050-099 |
| 770 | 22 | | PQ | N+ | 9-0 | 22-11-32 | D00479 | | 30 | | D04501P | | 2 | | 150-199, 275-299 |
| 770Z | | | | N+ | 0-0 | 22-11-32 | D00479 | | DED | | D04501P | DED | | | ALL |
| 771 | 20 | | PA | | 1-6 | 22-11-32 | D00479 | | 19 | | GD00313 | S.. | 2 | | ALL |
| 772 | 20 | | PA | | 1-6 | 22-11-32 | D00479 | | 18 | | GD00313 | D.. | 2 | | ALL |
| 773 | 22 | | PA | | 9-5 | 34-51-11 | D00157 | | 6 | | D05415P | | 5 | | 050-099 |
| 773 | 22 | | PA | | 10-0 | 34-51-11 | D00157 | | 6 | | D05415P | | 5 | | 150-199, 275-299 |
| 774 | 20 | | PA | | 1-6 | 34-51-11 | D00157 | | 14 | | GD00313 | D.. | 2 | | 050-099 |
| 774 | 20 | | PA | | 2-0 | 34-51-11 | D00157 | | 14 | | GD00313 | D.. | 2 | | 150-199, 275-299 |
| 775 | 24 | | PK | | 9-5 | 34-55-11 | D00157 | | 7 | | D05415P | | 1 | | 050-099 |
| 775 | 24 | | PK | | 10-0 | 34-55-11 | D00157 | | 7 | | D05415P | | 1 | | 150-199, 275-299 |
| 776 | 20 | | PA | | 1-6 | 34-55-11 | D00869 | | 6 | | GD00313 | D.. | 2 | | ALL |
| 777 | 20 | | PA | | 1-6 | 34-55-11 | D00869 | | 12 | | GD00313 | S.. | 2 | | ALL |
| 778 | 20 | | PA | | 6-2 | 31-41-16 | D05014J | | 6 | | GD00313 | D.. | 2 | | 050-099 |
| 778 | 20 | | PA | | 6-0 | 31-41-16 | D05014J | | 6 | | GD00313 | D.. | 2 | | 150-199, 275-299 |
| 779 | 20 | | PA | | 6-2 | 31-51-21 | D05014J | | 9 | | GD00313 | D.. | 2 | | 050-099 |
| 779 | 20 | | PA | | 6-0 | 31-51-21 | D05014J | | 9 | | GD00313 | D.. | 2 | | 150-199, 275-299 |
| 781 | 22 | | PA | | 11-5 | 34-22-81 | D05043P | | 1 | | TB0241Y | A010 | BJ | | 050-099 |
| 781 | 22 | | PA | | 15-0 | 34-22-81 | D05043P | | 1 | | TB0241Y | A010 | BJ | | 150-199, 275-299 |
| 782 | 20 | | PQ | O2 | 8-0 | 33-13-13 | TB0247Y | A001 | BJ | | D00647 | | 1 | | ALL |
| 782Z | | | | O2 | 0-0 | 33-13-13 | TB0247Y | | DED | | D00647 | DED | | | ALL |
| 783 | 20 | | PQ | O3 | 4-10 | 33-13-13 | GD03096 | A.. | 2 | | D00647 | | 2 | | 050-099 |
| 783 | 20 | | PQ | O3 | 5-0 | 33-13-13 | GD03096 | A.. | 2 | | D00647 | | 2 | | 150-199, 275-299 |
| 783Z | | | | O3 | 0-0 | 33-13-13 | GD03096 | | DED | | D00647 | DED | | | ALL |
| 784 | 18 | | PA | | 6-5 | 33-13-17 | D00869 | | 1 | DK | SP00351 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11
Section W0010
Page 18
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | | |
| 784 | 18 | | PA | 7-0 | 33-13-17 | D00869 | | 1 | DK | | | | SP00351 | | 9 | | 150-199, 275-299 |
| 785 | 18 | | PA | 1-11 | 33-13-17 | D00869 | | 2 | DK | | | | GD00313 | A.. | 2 | | 050-099 |
| 785 | 18 | | PA | 3-0 | 33-13-17 | D00869 | | 2 | DK | | | | GD00313 | A.. | 2 | | 150-199, 275-299 |
| 786 | 18 | | PA | 6-0 | 33-13-17 | D00479 | | 4 | DK | | | | SP00353 | | 9 | | ALL |
| 787 | 18 | | PA | 2-0 | 33-13-17 | D00479 | | 1 | DK | | | | GD00313 | A.. | 2 | | 050-099 |
| 787 | 18 | | PA | 3-0 | 33-13-17 | D00479 | | 1 | DK | | | | GD00313 | A.. | 2 | | 150-199, 275-299 |
| 788 | 24 | | PK | 5-0 | 33-14-21 | D05395P | | 11 | | | | | TB0247Y | A002 | BJ | | ALL |
| 789 | 24 | | PK | 6-0 | 33-14-21 | D05018J | | 3 | | | | | TB0247Y | A002 | BJ | | ALL |
| 790 | 24 | | PK | 12-0 | 33-14-21 | D05014J | | 10 | | | | | TB0247Y | A002 | BJ | | ALL |
| 791 | 22 | | PQ | P# | 5-0 | 33-16-12 | D04560P | | 5 | | | | TB0243Y | C016 | BJ | | ALL |
| 791Z | | | | P# | 0-0 | 33-16-12 | D04560P | | DED | | | | TB0243Y | DED | | | ALL |
| 792 | 22 | | PQ | P2 | 5-0 | 33-16-12 | D04560P | | 6 | | | | TB0247Z | 11 | BJ | | ALL |
| 792Z | | | | P2 | 0-0 | 33-16-12 | D04560P | | DED | | | | TB0247Z | DED | | | ALL |
| 793 | 22 | | PA | | 5-0 | 33-16-12 | D05395P | | 3 | | | | TB0243Y | A016 | BJ | | ALL |
| 794 | 22 | | PA | | 5-0 | 33-16-12 | D05395P | | 6 | | | | TB0247Z | 9 | BJ | | ALL |
| 795 | 22 | | PQ | P5 | 12-0 | 33-16-16 | D05014J | | 12 | | | | TB0247Z | 11 | BJ | | ALL |
| 795Z | | | | P5 | 0-0 | 33-16-16 | D05014J | | DED | | | | TB0247Z | DED | | | ALL |
| 796 | 22 | | PA | | 12-0 | 33-16-16 | D05014J | | 13 | | | | TB0247Z | 9 | BJ | | ALL |
| 800B | 24 | | PW | QT | 3-6 | 31-31-20 | D05255P | | 11 | | | | TB0245Z | 2 | BJ | | 050-099 |
| 800B | 24 | | PW | QO | 4-0 | 31-31-20 | D05255P | | 11 | | | | TB0245Z | 2 | BJ | | 150-199, 275-299 |
| 800R | 24 | | PW | QT | 0-0 | 31-31-20 | D05255P | | 10 | | | | TB0245Z | 1 | BJ | | 050-099 |
| 800R | 24 | | PW | QO | 0-0 | 31-31-20 | D05255P | | 10 | | | | TB0245Z | 1 | BJ | | 150-199, 275-299 |
| 800Z | | | | QT | 0-0 | 31-31-20 | D05255P | | 12 | | | | TB0241Y | DED | | | 050-099 |
| 800Z | | | | QO | 0-0 | 31-31-20 | D05255P | | 12 | | | | TB0245Z | REF | | JC | 150-199, 275-299 |
| 801 | 24 | | PK | | 3-1 | 34-61-15 | SM00023 | | | W | | | D04147P | 41 | | | 050-099 |
| 801 | 24 | | PK | | 4-0 | 34-61-15 | SM00023 | | | W | | | D04147P | 41 | | | 150-199 |
| 801 | 24 | | PK | | 4-0 | 34-61-15 | SM00023 | | 9 | | | | D04147P | 41 | | | 275-299 |
| 804 | 22 | | PA | | 5-0 | 34-22-38 | D04283P | | 20 | | | | D04147P | 36 | | | 050-099 |
| 804 | 22 | | PA | | 6-0 | 34-22-38 | D04283P | | 20 | | | | D04147P | 36 | | | 150-199, 275-299 |
| 805 | 22 | | PA | | 9-0 | 33-16-15 | D05305P | | 40 | | | | TB0243Y | C016 | BJ | | ALL |
| 806 | 18 | | PA | | 7-3 | 33-13-13 | D05305P | | 11 | DK | | | SP00347 | | 9 | | 050-099 |
| 806 | 18 | | PA | | 7-0 | 33-13-13 | D05305P | | 11 | DK | | | SP00347 | | 9 | | 150-199, 275-299 |
| 807 | 18 | | PA | | 6-5 | 33-13-13 | D05305P | | 13 | DK | | | GD03096 | A.. | 2 | | 050-099 |
| 807 | 18 | | PA | | 7-0 | 33-13-13 | D05305P | | 13 | DK | | | GD03096 | A.. | 2 | | 150-199, 275-299 |
| 808 | 22 | | PA | | 3-2 | 34-22-36 | D04167P | | 16 | | | | SM00009 | | W | | 050-099 |
| 808 | 22 | | PA | | 4-0 | 34-22-36 | D04167P | | 16 | | | | SM00009 | | W | | 150-199, 275-299 |
| 809 | 22 | | PA | | 4-0 | 34-22-36 | D00645 | | 17 | | | | SM00009 | | W | | ALL |
| 810 | 22 | | PA | | 6-9 | 34-22-36 | D05305P | | 37 | | | | SM00009 | | W | | 050-099 |
| 810 | 22 | | PA | | 7-0 | 34-22-36 | D05305P | | 37 | | | | SM00009 | | W | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 19

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 811 | 20 | | PA | | 8-0 | 34-22-36 | D05305P | | 38 | | GD00077 | D.. | 2 | | ALL |
| 812 | 20 | | PA | | 7-3 | 33-13-13 | D05305P | | 39 | | SP00347 | | 9 | | 050-099 |
| 812 | 20 | | PA | | 7-0 | 33-13-13 | D05305P | | 39 | | SP00347 | | 9 | | 150-199, 275-299 |
| 813 | 22 | | PA | | 9-0 | 34-22-36 | D00647 | | 17 | | SP00365 | | 9 | | ALL |
| 818 | 20 | | PA | | 7-1 | 22-11-12 | D00475 | | 11 | | GD00059 | D.. | 2 | | 050-099 |
| 818 | 20 | | PA | | 7-0 | 22-11-12 | D00475 | | 11 | | GD00059 | D.. | 2 | | 150-199, 275-299 |
| 819 | 20 | | PA | | 4-4 | 34-22-17 | D04283P | | 27 | | GD00063 | D.. | 2 | | 050-099 |
| 819 | 20 | | PA | | 5-0 | 34-22-17 | D04283P | | 27 | | GD00063 | D.. | 2 | | 150-199, 275-299 |
| 820 | 24 | | PK | | 2-6 | 34-61-16 | D04283P | | 3 | | SM00023 | | W | | 050-099 |
| 820 | 24 | | PK | | 4-0 | 34-61-16 | D04283P | | 3 | | SM00023 | | W | | 150-199 |
| 820 | 24 | | PK | | 4-0 | 34-61-16 | D04283P | | 3 | | SM00023 | | 9 | | 275-299 |
| 821 | 20 | | PA | | 4-1 | 34-61-16 | D04283P | | 34 | | GD00059 | D.. | 2 | | 050-099 |
| 821 | 20 | | PA | | 5-0 | 34-61-16 | D04283P | | 34 | | GD00059 | D.. | 2 | | 150-199, 275-299 |
| 822 | 20 | | PA | | 4-1 | 34-61-16 | D04283P | | 51 | | GD00059 | D.. | 2 | | 050-099 |
| 822 | 20 | | PA | | 5-0 | 34-61-16 | D04283P | | 51 | | GD00059 | D.. | 2 | | 150-199, 275-299 |
| 823 | 20 | | PA | | 4-1 | 34-61-16 | D04283P | | 52 | | GD00059 | D.. | 2 | | 050-099 |
| 823 | 20 | | PA | | 5-0 | 34-61-16 | D04283P | | 52 | | GD00059 | D.. | 2 | | 150-199, 275-299 |
| 824 | 24 | | PK | | 2-6 | 34-61-16 | D04283P | | 53 | | SM00035 | | W | | 050-099 |
| 824 | 24 | | PK | | 4-0 | 34-61-16 | D04283P | | 53 | | SM00035 | | W | | 150-199, 275-299 |
| 825 | 24 | | PK | | 3-0 | 34-61-16 | SM00035 | | | W | D05255P | | 24 | | 050-099 |
| 825 | 24 | | PK | | 4-0 | 34-61-16 | D05255P | | 24 | | SM00035 | | W | | 150-199, 275-299 |
| 826 | 24 | | PK | | 3-0 | 34-61-16 | SM00023 | | | W | D05255P | | 19 | | 050-099 |
| 826 | 24 | | PK | | 4-0 | 34-61-16 | D05255P | | 19 | | SM00023 | | W | | 150-199 |
| 826 | 24 | | PK | | 4-0 | 34-61-16 | D05255P | | 19 | | SM00023 | | 9 | | 275-299 |
| 827 | 24 | | PK | | 3-1 | 31-31-13 | D04147P | | 21 | | SM00023 | | W | | 050-099 |
| 827 | 24 | | PK | | 4-0 | 31-31-13 | D04147P | | 21 | | SM00023 | | W | | 150-199 |
| 827 | 24 | | PK | | 4-0 | 31-31-13 | D04147P | | 21 | | SM00023 | | 9 | | 275-299 |
| 828 | 24 | | PK | | 3-1 | 31-31-13 | D04147P | | 22 | | SM00035 | | W | | 050-099 |
| 828 | 24 | | PK | | 4-0 | 31-31-13 | D04147P | | 22 | | SM00035 | | W | | 150-199, 275-299 |
| 829 | 22 | | PA | | 4-9 | 34-61-16 | SP00365 | | | 9 | D05809P | | 9 | | 050-099 |
| 829 | 22 | | PA | | 5-0 | 34-61-16 | D05809P | | 9 | | SP00365 | | 9 | | 150-199, 275-299 |
| 830 | 20 | | PA | | 4-1 | 34-61-16 | D04283P | | 54 | | GD00059 | D.. | 2 | | 050-099 |
| 830 | 20 | | PA | | 5-0 | 34-61-16 | D04283P | | 54 | | GD00059 | D.. | 2 | | 150-199, 275-299 |
| 831 | 24 | | PK | | 5-0 | 34-61-16 | D04283P | | 55 | | D04147P | | 20 | | 050-099 |
| 831 | 24 | | PK | | 6-0 | 34-61-16 | D04283P | | 55 | | D04147P | | 20 | | 150-199, 275-299 |
| 832 | 24 | | PK | | 9-7 | 31-31-26 | D05305P | | 35 | | D04171P | | 17 | | 050-099 |
| 832 | 24 | | PK | | 10-0 | 31-31-26 | D05305P | | 35 | | D04171P | | 17 | | 150-199, 275-299 |
| 879 | 22 | | PA | | 7-5 | 34-45-14 | D04171P | | 23 | | D00113 | CAP | Y | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 20

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0011 | 286T0011 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | |
| 879 | 22 | | PA | 9-0 | 34-45-14 | D04171P | | 23 | | | | D00113 | CAP | Y | | 150-152, 155-156, 162-166, 275-276 |
| 879 | 22 | | PA | 9-0 | 34-45-14 | D04167P | | 53 | | | | D00113 | CAP | Y | | 153-154 |
| 880 | 22 | | PA | 7-5 | 34-45-14 | D04171P | | 22 | | | | D00113 | 28 | | | 050-099 |
| 880 | 22 | | PA | 9-0 | 34-45-14 | D04171P | | 22 | | | | D00113 | 28 | | | 150-152, 155-199, 275-299 |
| 880 | 22 | | PA | 9-0 | 34-45-14 | D04167P | | 31 | | | | D00113 | 28 | | | 153-154 |
| 885 | 20 | | PA | 4-1 | 34-61-16 | D04283P | | 48 | | | | GD00059 | D.. | 2 | | 051-099 |
| 885 | 20 | | PA | 5-0 | 34-61-16 | D04283P | | 48 | | | | GD00059 | D.. | 2 | | 155-199, 275-299 |
| 886 | 20 | | PA | 4-1 | 34-61-16 | D04283P | | 49 | | | | GD00059 | D.. | 2 | | 051-099 |
| 886 | 20 | | PA | 5-0 | 34-61-16 | D04283P | | 49 | | | | GD00059 | D.. | 2 | | 155-199, 275-299 |
| 890 | 24 | | PK | 11-3 | 34-61-26 | D05043P | | 9 | | | | D05255P | 26 | | | 050-099 |
| 890 | 24 | | PK | 12-0 | 34-61-26 | D05043P | | 9 | | | | D05255P | 26 | | | 155-199, 275-299 |
| 891 | 24 | | PK | 4-11 | 34-61-16 | D04283P | | 28 | | | | D05255P | 25 | | | 050-099 |
| 891 | 24 | | PK | 6-0 | 34-61-16 | D04283P | | 28 | | | | D05255P | 25 | | | 155-199, 275-299 |
| 892 | 20 | | PA | 3-0 | 34-61-26 | D05043P | | 12 | | | | GD03096 | D.. | 2 | | 051-099, 155-199, 275-299 |
| 893 | 20 | | PA | 3-0 | 34-61-16 | D05043P | | 13 | | | | GD03096 | D.. | 2 | | 051-099 |
| 893 | 20 | | PA | 3-0 | 34-61-26 | D05043P | | 13 | | | | GD03096 | D.. | 2 | | 155-199, 275-299 |
| 901 | 22 | | PA | 2-0 | 34-22-92 | D00717 | | 18 | | | | D00717 | 37 | | | 050-099 |
| 901 | 22 | | PA | 2-0 | 34-22-82 | D00113 | | 18 | | | | D00113 | 37 | | | 150-199, 275-299 |
| 926 | 18 | | PA | 5-0 | 33-13-11 | SP00355 | | | | 9 | | SPZ0002 | | S | | 150, 152-199, 275-299 |
| FRA | | | | 0-0 | 73-21-14 | D10122 | | | REF | | UJ | D10122 | 20 | | | 150-199, 275-299 |
| FRI | | | | 0-0 | 73-21-14 | D10122 | | | | | UI | D10122 | 20 | | | 050-099 |
| FRM | | | | 0-0 | 34-22-91 | TB0241Y | | | | | FM | TB0241X | C006 | BJ | | ALL |
| FRO | | | | 0-0 | 34-22-91 | TB0243Y | | | | | KC | TB0243X | D004 | BJ | | ALL |
| FRR | | | | 0-0 | 34-22-91 | TB0243Y | | | | | IR | TB0243X | C008 | BJ | | ALL |
| FRS | | | | 0-0 | 34-22-91 | TB0243Y | | | | | IS | TB0243X | B007 | BJ | | ALL |
| FRW | | | | 0-0 | 34-13-11 | TB0241Y | | | | | JW | TB0241X | C011 | BJ | | 050-099, 150-199 |
| FRW | | | | 0-0 | 34-13-11 | TB0241X | | | C011 | BJ | | TB0241Y | REF | | JW | 275-299 |
| W0013 | 286T0013 | | | P1-3 CAPT INSTR PNL-R | | | | | | | | | | | | |
| 001 | 22 | | PA | 2-8 | 34-32-11 | D04285J | | 1 | | | | L00587 | 2 | 1A | | ALL |
| 002 | 22 | | PA | 2-8 | 34-32-11 | D04285J | | 2 | | | | L00586 | 2 | 1A | | ALL |
| 003 | 22 | | PA | 2-9 | 34-32-11 | D04285J | | 3 | | | | L00585 | 2 | 1A | | ALL |
| 004 | 22 | | PQ | AD | 1-10 | 33-16-13 | D04285J | | 4 | | | D04580P | 53 | | | ALL |
| 004Z | | | | AD | 0-0 | 33-16-13 | D04285J | | DED | | | D04580P | DED | | | ALL |
| 005 | 22 | | PQ | AE | 1-10 | 33-16-13 | D04285J | | 5 | | | D04580P | 55 | | | ALL |
| 005Z | | | | AE | 0-0 | 33-16-13 | D04285J | | DED | | | D04580P | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 21

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0013 | 286T0013 | | | P1-3 CAPT INSTR PNL-R (continued) | | | | | | | | | | | | |
| 006 | 22 | PQ | AF | | 2-10 | 33-16-13 | D04580P | | 5 | | | L00585 | 1 | 1A | | ALL |
| 006Z | | | AF | | 0-0 | 33-16-13 | L00585 | | DED | | | D04580P | DED | | | ALL |
| 007 | 22 | PA | | | 2-4 | 33-16-13 | D04586P | | 12 | | | L00585 | 3 | 1A | | ALL |
| 008 | 22 | PQ | AH | | 2-9 | 33-16-13 | D04580P | | 6 | | | L00586 | 1 | 1A | | ALL |
| 008Z | | | AH | | 0-0 | 33-16-13 | L00586 | | DED | | | D04580P | DED | | | ALL |
| 009 | 22 | PA | | | 2-3 | 33-16-13 | D04586P | | 24 | | | L00586 | 3 | 1A | | ALL |
| 010 | 22 | PQ | AJ | | 2-9 | 33-16-13 | D04580P | | 7 | | | L00587 | 1 | 1A | | ALL |
| 010Z | | | AJ | | 0-0 | 33-16-13 | L00587 | | DED | | | D04580P | DED | | | ALL |
| 011 | 22 | PA | | | 2-3 | 33-16-13 | D04586P | | 25 | | | L00587 | 3 | 1A | | ALL |
| 012 | 22 | PA | | | 2-10 | 29-21-32 | D04285J | | 12 | | | S00547 | 2 | 1A | | ALL |
| 016 | 22 | PA | | | 2-10 | 29-21-32 | S00547 | | 16 | 1A | | D04285J | 17 | | | ALL |
| 017 | 22 | PA | | | 2-10 | 29-21-32 | D04285J | | 10 | | | S00547 | 9 | 1A | | ALL |
| 018 | 22 | PA | | | 2-10 | 29-21-32 | D04285J | | 15 | | | S00547 | 3 | 1A | | ALL |
| 019 | 22 | PA | | | 2-10 | 29-21-32 | D04285J | | 13 | | | S00547 | 6 | 1A | | ALL |
| 020 | 22 | PA | | | 2-10 | 29-21-32 | D04285J | | 14 | | | S00547 | 5 | 1A | | ALL |
| 021 | 20 | PA | | | 1-11 | 33-13-11 | D04285J | | 6 | | | SM00006 | | W | | ALL |
| 022 | 20 | PA | | | 1-11 | 33-13-11 | D04285J | | 7 | | | SM00007 | | W | | ALL |
| 023 | 22 | PA | | | 2-6 | 33-16-13 | D04285J | | 8 | | | D04586P | 55 | | | ALL |
| 024 | 22 | PQ | AX | | 3-4 | 33-16-13 | D04586P | | 18 | | | L00474 | 1 | 1A | | ALL |
| 024Z | | | AX | | 0-0 | 33-16-13 | D04586P | | DED | | | L00474 | DED | | | ALL |
| 025 | 22 | PQ | AY | | 2-5 | 33-16-13 | D04586P | | 5 | | | L00605 | 1 | 1A | | ALL |
| 025Z | | | AY | | 0-0 | 33-16-13 | D04586P | | DED | | | L00605 | DED | | | ALL |
| 026 | 22 | PQ | BA | | 2-5 | 33-16-13 | D04586P | | 26 | | | L00605 | 3 | 1A | | ALL |
| 026Z | | | BA | | 0-0 | 33-16-13 | D04586P | | DED | | | L00605 | DED | | | ALL |
| 027 | 22 | PQ | BB | | 2-5 | 33-16-13 | D04586P | | 6 | | | S00547 | 18 | 1A | | ALL |
| 027Z | | | BB | | 0-0 | 33-16-13 | D04586P | | DED | | | S00547 | DED | | | ALL |
| 028 | 22 | PQ | BC | | 2-5 | 33-16-13 | D04586P | | 43 | | | S00547 | 17 | 1A | | ALL |
| 028Z | | | BC | | 0-0 | 33-16-13 | D04586P | | DED | | | S00547 | DED | | | ALL |
| 030 | 22 | PQ | BE | | 2-7 | 32-41-11 | D04513J | | 3 | | | L00605 | 2 | 1A | | ALL |
| 030Z | | | BE | | 0-0 | 32-41-11 | D04513J | | DED | | | L00605 | DED | | | ALL |
| 031 | 20 | PA | | | 1-5 | 33-13-11 | SM00006 | | | W | | S00547 | 13 | 1A | | ALL |
| 032 | 20 | PA | | | 1-5 | 33-13-11 | SM00007 | | | W | | S00547 | 15 | 1A | | ALL |
| 033 | 20 | PA | | | 1-5 | 33-13-11 | SM00006 | | | W | | L00609 | = P | B | | ALL |
| 034 | 20 | PA | | | 2-10 | 33-13-11 | SM00007 | | | W | | GDY0001 | A.. | E | | ALL |
| 040 | 20 | PA | | | 2-10 | 29-21-32 | S00547 | | 8 | 1A | | D04285J | 22 | | | ALL |
| 050 | 22 | PA | | | 1-11 | 31-41-12 | S10170 | | 1C | Z2 | | SM00021 | | W | | ALL |
| 051 | 22 | PA | | | 1-7 | 31-41-12 | D04285J | | 25 | | | SM00021 | | W | | ALL |
| 052 | 22 | PA | | | 2-8 | 31-41-12 | D04285J | | 26 | | | S10170 | 1NO | Z2 | | ALL |
| 053 | 22 | PA | | | 2-8 | 31-41-12 | D04285J | | 27 | | | S10230 | 2NO | Z2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0010
Page 22
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0013 | 286T0013 | | | P1-3 CAPT INSTR PNL-R (continued) | | | | | | | | | | | | | | |
| 054 | 22 | | PA | | 1-11 | 31-41-12 | SM00021 | | | | | | W | S10230 | 2C | Z2 | | ALL |
| 055 | 24 | | PV | CE | 3-0 | 22-14-11 | D05107J | | | 1 | | | | L00019 | 2 | 1A | | ALL |
| 055Z | | | | CE | 0-0 | 22-14-11 | D05107J | | | DED | | | | L00019 | DED | | | ALL |
| 056 | 24 | | PV | CF | 3-0 | 22-14-11 | D05107J | | | 2 | | | | M00779 | D5 | 1A | | ALL |
| 056Z | | | | CF | 0-0 | 22-14-11 | D05107J | | | DED | | | | M00779 | DED | | | ALL |
| 057 | 24 | | PV | CG | 2-9 | 22-14-11 | D04513J | | | 1 | | | | M00779 | D2 | 1A | | ALL |
| 057Z | | | | CG | 0-0 | 22-14-11 | D04513J | | | DED | | | | M00779 | DED | | | ALL |
| 058 | 22 | | PA | | 2-6 | 22-34-11 | D04285J | | | 28 | | | | L00591 | 2 | 1A | | ALL |
| 059 | 24 | | PK | | 2-5 | 34-12-12 | M00779 | | | F5 | 1A | | | D04285J | 29 | | | ALL |
| 062 | 22 | | PA | | 2-6 | 34-61-15 | D04285J | | | 30 | | | | L00603 | 2 | 1A | | ALL |
| 063 | 24 | | PK | | 2-0 | 31-51-42 | M00779 | | | B2 | 1A | | | SM00011 | | | | ALL |
| 064 | 24 | | PK | | 2-0 | 31-51-42 | M00779 | | | B5 | 1A | | | SM00011 | | | | ALL |
| 065 | 24 | | PK | | 1-11 | 31-51-42 | D04285J | | | 31 | | | | SM00011 | | | | ALL |
| 066 | 24 | | PK | | 2-5 | 34-16-11 | D04285J | | | 32 | | | | L00136 | 2 | 1A | | ALL |
| 067 | 22 | | PA | | 2-0 | 34-46-11 | M00779 | | | C2 | 1A | | | SM00012 | | | | ALL |
| 068 | 22 | | PA | | 2-0 | 34-46-11 | M00779 | | | C5 | 1A | | | SM00012 | | | | ALL |
| 069 | 22 | | PA | | 1-11 | 34-46-11 | D04285J | | | 33 | | | | SM00012 | | | | ALL |
| 070 | 22 | | PA | | 1-10 | 34-46-11 | S00016 | | | 16 | 1A | | | SM00013 | | | | ALL |
| 071 | 22 | | PA | | 1-10 | 34-46-11 | S00016 | | | 15 | 1A | | | SM00013 | | | | ALL |
| 072 | 22 | | PA | | 1-7 | 34-46-11 | D04285J | | | 34 | | | | SM00013 | | | | ALL |
| 073 | 24 | | PK | | 2-6 | 34-46-11 | D04285J | | | 35 | | | | S00016 | 2 | 1A | | ALL |
| 074 | 22 | | PA | | 2-6 | 34-46-11 | D04285J | | | 36 | | | | S00016 | 3 | 1A | | ALL |
| 075 | 24 | | PV | CY | 3-0 | 34-12-22 | D05107J | | | 4 | | | | M00779 | F2 | 1A | | ALL |
| 075Z | | | | CY | 0-0 | 34-12-22 | D05107J | | | DED | | | | M00779 | DED | | | ALL |
| 076 | 20 | | PA | | 2-6 | 33-13-11 | L00494 | | | = P | B | | | SM00015 | | | | ALL |
| 077 | 20 | | PA | | 1-11 | 33-13-11 | L00662 | | | = P | B | | | SM00015 | | | | ALL |
| 078 | 20 | | PA | | 1-7 | 33-13-11 | D04513J | | | 4 | | | | SM00015 | | | | ALL |
| 079 | 22 | | PQ | DD | 2-5 | 33-16-13 | SM00014 | | | | 9 | | | L00474 | 3 | 1A | | 050-099, 150-154, 162-165, 275-276 |
| 079 | 22 | | PQ | DD | 2-5 | 33-16-13 | SM00014 | | | | W | | | L00474 | 3 | 1A | | 155-157, 166-199, 277-299 |
| 079Z | | | | DD | 0-0 | 33-16-13 | SM00014 | | | DED | | | | L00474 | DED | | | ALL |
| 080 | 22 | | PQ | DE | 2-3 | 33-16-13 | SM00014 | | | | 9 | | | L00475 | 3 | 1A | | 050-099, 150-154, 162-165, 275-276 |
| 080 | 22 | | PQ | DE | 2-3 | 33-16-13 | SM00014 | | | | W | | | L00475 | 3 | 1A | | 155-157, 166-199, 277-299 |
| 080Z | | | | DE | 0-0 | 33-16-13 | SM00014 | | | DED | | | | L00475 | DED | | | ALL |
| 081 | 22 | | PQ | DF | 1-8 | 33-16-13 | D04586P | | | 53 | | | | D04513J | 14 | | | ALL |
| 081Z | | | | DF | 0-0 | 33-16-13 | D04586P | | | DED | | | | D04513J | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 23

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0013 | 286T0013 | | | | P1-3 CAPT INSTR PNL-R (continued) | | | | | | | | | | | |
| 082 | 22 | PQ | DG | | 1-7 | 33-16-13 | SM00014 | | | 9 | | | D04513J | 15 | | 050-099, 150-154, 162-165, 275-276 |
| 082 | 22 | PQ | DG | | 1-7 | 33-16-13 | SM00014 | | | W | | | D04513J | 15 | | 155-157, 166-199, 277-299 |
| 082Z | | | DG | | 0-0 | 33-16-13 | SM00014 | DED | | | | | D04513J | DED | | ALL |
| 083 | 22 | PQ | DH | | 3-2 | 33-16-13 | D04586P | 16 | | | | | L00475 | 1 | 1A | ALL |
| 083Z | | | DH | | 0-0 | 33-16-13 | D04586P | DED | | | | | L00475 | DED | | ALL |
| 084 | 22 | PQ | DI | | 1-11 | 33-16-13 | D05107J | 7 | | | | | D04586P | 51 | | ALL |
| 084Z | | | DI | | 0-0 | 33-16-13 | D05107J | DED | | | | | D04586P | DED | | ALL |
| 085 | 22 | PQ | DJ | | 2-9 | 33-16-13 | D04513J | 16 | | | | | D04580P | 44 | | ALL |
| 085Z | | | DJ | | 0-0 | 33-16-13 | D04513J | DED | | | | | D04580P | DED | | ALL |
| 086 | 22 | PQ | DK | | 3-0 | 33-16-13 | D05107J | 9 | | | | | D04580P | 51 | | ALL |
| 086Z | | | DK | | 0-0 | 33-16-13 | D05107J | DED | | | | | D04580P | DED | | ALL |
| 087 | 22 | PQ | DL | | 2-7 | 33-16-13 | M00779 | A3 | 1A | | | | D04586P | 1 | | ALL |
| 087Z | | | DL | | 0-0 | 33-16-13 | M00779 | DED | | | | | D04586P | DED | | ALL |
| 088 | 22 | PQ | DM | | 2-7 | 33-16-13 | M00779 | A6 | 1A | | | | D04586P | 13 | | ALL |
| 088Z | | | DM | | 0-0 | 33-16-13 | M00779 | DED | | | | | D04586P | DED | | ALL |
| 089 | 22 | PQ | DN | | 2-7 | 33-16-13 | M00779 | B3 | 1A | | | | D04586P | 2 | | ALL |
| 089Z | | | DN | | 0-0 | 33-16-13 | M00779 | DED | | | | | D04586P | DED | | ALL |
| 090 | 22 | PQ | DO | | 2-7 | 33-16-13 | M00779 | B6 | 1A | | | | D04586P | 14 | | ALL |
| 090Z | | | DO | | 0-0 | 33-16-13 | M00779 | DED | | | | | D04586P | DED | | ALL |
| 091 | 22 | PQ | DP | | 2-7 | 33-16-13 | M00779 | C3 | 1A | | | | D04586P | 3 | | ALL |
| 091Z | | | DP | | 0-0 | 33-16-13 | M00779 | DED | | | | | D04586P | DED | | ALL |
| 092 | 22 | PA | | | 2-7 | 33-16-13 | M00779 | C6 | 1A | | | | D04586P | 8 | | ALL |
| 093 | 22 | PQ | DR | | 2-7 | 33-16-13 | M00779 | D3 | 1A | | | | D04586P | 4 | | ALL |
| 093Z | | | DR | | 0-0 | 33-16-13 | M00779 | DED | | | | | D04586P | DED | | ALL |
| 094 | 22 | PQ | DS | | 2-7 | 33-16-13 | M00779 | D6 | 1A | | | | D04586P | 15 | | ALL |
| 094Z | | | DS | | 0-0 | 33-16-13 | M00779 | DED | | | | | D04586P | DED | | ALL |
| 095 | 22 | PQ | DT | | 2-7 | 33-16-13 | M00779 | E3 | 1A | | | | D04586P | 10 | | ALL |
| 095Z | | | DT | | 0-0 | 33-16-13 | M00779 | DED | | | | | D04586P | DED | | ALL |
| 096 | 22 | PA | | | 2-7 | 33-16-13 | M00779 | E6 | 1A | | | | D04586P | 9 | | ALL |
| 097 | 22 | PQ | DV | | 2-7 | 33-16-13 | M00779 | F3 | 1A | | | | D04586P | 11 | | ALL |
| 097Z | | | DV | | 0-0 | 33-16-13 | M00779 | DED | | | | | D04586P | DED | | ALL |
| 098 | 22 | PQ | DW | | 2-7 | 33-16-13 | M00779 | F6 | 1A | | | | D04586P | 27 | | ALL |
| 098Z | | | DW | | 0-0 | 33-16-13 | M00779 | DED | | | | | D04586P | DED | | ALL |
| 099 | 22 | PQ | DX | | 2-8 | 33-16-13 | L00591 | 3 | 1A | | | | D04586P | 28 | | ALL |
| 099Z | | | DX | | 0-0 | 33-16-13 | L00591 | DED | | | | | D04586P | DED | | ALL |
| 101 | 22 | PA | | | 2-6 | 34-46-11 | L00890 | 2 | 1A | | | | D04285J | 23 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0010
Page 24
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0013 | 286T0013 | | | P1-3 CAPT INSTR PNL-R (continued) | | | | | | | | | | | | |
| 109 | 22 | PQ | EI | 1-5 | 33-16-13 | SM00014 | | | | 9 | | | D04586P | 44 | | 050-099, 150-154, 162-165, 275-276 |
| 109 | 22 | PQ | EI | 1-5 | 33-16-13 | SM00014 | | | | W | | | D04586P | 44 | | 155-157, 166-199, 277-299 |
| 109Z | | | EI | 0-0 | 33-16-13 | SM00014 | DED | | | | | | D04586P | DED | | ALL |
| 125 | 22 | PA | | 2-8 | 33-16-13 | L00890 | | 3 | 1A | | | | D04586P | 19 | | ALL |
| 126 | 22 | PQ | FA | 2-8 | 33-16-13 | L00603 | | 3 | 1A | | | | D04586P | 29 | | ALL |
| 126Z | | | FA | 0-0 | 33-16-13 | L00603 | DED | | | | | | D04586P | DED | | ALL |
| 127 | 22 | PA | | 2-9 | 33-16-13 | S00016 | | 14 | 1A | | | | D04586P | 20 | | ALL |
| 128 | 22 | PA | | 2-9 | 33-16-13 | S00016 | | 17 | 1A | | | | D04586P | 21 | | ALL |
| 129 | 22 | PQ | FD | 2-7 | 33-16-13 | L00136 | | 3 | 1A | | | | D04586P | 30 | | ALL |
| 129Z | | | FD | 0-0 | 33-16-13 | L00136 | DED | | | | | | D04586P | DED | | ALL |
| 130 | 22 | PA | | 2-8 | 33-16-13 | L00716 | | 3 | 1A | | | | D04586P | 22 | | ALL |
| 131 | 22 | PQ | FF | 3-3 | 33-16-13 | L00119 | | 3 | 1A | | | | D04586P | 31 | | ALL |
| 131Z | | | FF | 0-0 | 33-16-13 | L00119 | DED | | | | | | D04586P | DED | | ALL |
| 132 | 22 | PQ | FG | 2-7 | 33-16-13 | L00019 | | 3 | 1A | | | | D04586P | 32 | | ALL |
| 132Z | | | FG | 0-0 | 33-16-13 | L00019 | DED | | | | | | D04586P | DED | | ALL |
| 133 | 22 | PQ | FH | 2-6 | 33-16-13 | M00779 | | A1 | 1A | | | | D04580P | 1 | | ALL |
| 133Z | | | FH | 0-0 | 33-16-13 | M00779 | DED | | | | | | D04580P | DED | | ALL |
| 134 | 22 | PQ | FI | 2-6 | 33-16-13 | M00779 | | A4 | 1A | | | | D04580P | 13 | | ALL |
| 134Z | | | FI | 0-0 | 33-16-13 | M00779 | DED | | | | | | D04580P | DED | | ALL |
| 135 | 22 | PQ | FJ | 2-6 | 33-16-13 | M00779 | | B1 | 1A | | | | D04580P | 2 | | ALL |
| 135Z | | | FJ | 0-0 | 33-16-13 | M00779 | DED | | | | | | D04580P | DED | | ALL |
| 136 | 22 | PQ | FK | 2-6 | 33-16-13 | M00779 | | B4 | 1A | | | | D04580P | 14 | | ALL |
| 136Z | | | FK | 0-0 | 33-16-13 | M00779 | DED | | | | | | D04580P | DED | | ALL |
| 137 | 22 | PQ | FL | 2-6 | 33-16-13 | M00779 | | C1 | 1A | | | | D04580P | 3 | | ALL |
| 137Z | | | FL | 0-0 | 33-16-13 | M00779 | DED | | | | | | D04580P | DED | | ALL |
| 138 | 22 | PQ | FM | 2-6 | 33-16-13 | M00779 | | C4 | 1A | | | | D04580P | 8 | | ALL |
| 138Z | | | FM | 0-0 | 33-16-13 | M00779 | DED | | | | | | D04580P | DED | | ALL |
| 139 | 22 | PQ | FN | 2-6 | 33-16-13 | M00779 | | D1 | 1A | | | | D04580P | 4 | | ALL |
| 139Z | | | FN | 0-0 | 33-16-13 | M00779 | DED | | | | | | D04580P | DED | | ALL |
| 140 | 22 | PQ | FO | 2-6 | 33-16-13 | M00779 | | D4 | 1A | | | | D04580P | 15 | | ALL |
| 140Z | | | FO | 0-0 | 33-16-13 | M00779 | DED | | | | | | D04580P | DED | | ALL |
| 141 | 22 | PQ | FP | 2-6 | 33-16-13 | M00779 | | E1 | 1A | | | | D04580P | 10 | | ALL |
| 141Z | | | FP | 0-0 | 33-16-13 | M00779 | DED | | | | | | D04580P | DED | | ALL |
| 142 | 22 | PQ | FQ | 2-6 | 33-16-13 | M00779 | | E4 | 1A | | | | D04580P | 9 | | ALL |
| 142Z | | | FQ | 0-0 | 33-16-13 | M00779 | DED | | | | | | D04580P | DED | | ALL |
| 143 | 22 | PQ | FR | 2-6 | 33-16-13 | M00779 | | F1 | 1A | | | | D04580P | 11 | | ALL |
| 143Z | | | FR | 0-0 | 33-16-13 | M00779 | DED | | | | | | D04580P | DED | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 25

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0013 | 286T0013 | | | P1-3 CAPT INSTR PNL-R (continued) | | | | | | | | | | | |
| 144 | 22 | PQ | FS | | 2-6 | 33-16-13 | M00779 | F4 | 1A | | D04580P | 27 | | | ALL |
| 144Z | | | FS | | 0-0 | 33-16-13 | M00779 | DED | | | D04580P | DED | | | ALL |
| 145 | 22 | PQ | FT | | 2-6 | 33-16-13 | L00591 | 1 | 1A | | D04580P | 28 | | | ALL |
| 145Z | | | FT | | 0-0 | 33-16-13 | L00591 | DED | | | D04580P | DED | | | ALL |
| 146 | 22 | PQ | FU | | 2-6 | 33-16-13 | L00890 | 1 | 1A | | D04580P | 19 | | | ALL |
| 146Z | | | FU | | 0-0 | 33-16-13 | L00890 | DED | | | D04580P | DED | | | ALL |
| 147 | 22 | PQ | FV | | 2-6 | 33-16-13 | L00603 | 1 | 1A | | D04580P | 29 | | | ALL |
| 147Z | | | FV | | 0-0 | 33-16-13 | L00603 | DED | | | D04580P | DED | | | ALL |
| 148 | 22 | PQ | FW | | 2-7 | 33-16-13 | S00016 | 13 | 1A | | D04580P | 20 | | | ALL |
| 148Z | | | FW | | 0-0 | 33-16-13 | S00016 | DED | | | D04580P | DED | | | ALL |
| 149 | 22 | PQ | FX | | 2-7 | 33-16-13 | S00016 | 18 | 1A | | D04580P | 21 | | | ALL |
| 149Z | | | FX | | 0-0 | 33-16-13 | S00016 | DED | | | D04580P | DED | | | ALL |
| 150 | 22 | PQ | FY | | 2-6 | 33-16-13 | L00136 | 1 | 1A | | D04580P | 30 | | | ALL |
| 150Z | | | FY | | 0-0 | 33-16-13 | L00136 | DED | | | D04580P | DED | | | ALL |
| 151 | 22 | PQ | GA | | 2-6 | 33-16-13 | L00716 | 1 | 1A | | D04580P | 22 | | | ALL |
| 151Z | | | GA | | 0-0 | 33-16-13 | L00716 | DED | | | D04580P | DED | | | ALL |
| 152 | 22 | PQ | GB | | 2-7 | 33-16-13 | L00119 | 1 | 1A | | D04580P | 31 | | | ALL |
| 152Z | | | GB | | 0-0 | 33-16-13 | L00119 | DED | | | D04580P | DED | | | ALL |
| 153 | 22 | PQ | GC | | 2-6 | 33-16-13 | L00019 | 1 | 1A | | D04580P | 32 | | | ALL |
| 153Z | | | GC | | 0-0 | 33-16-13 | L00019 | DED | | | D04580P | DED | | | ALL |
| 154 | 22 | PA | | | 2-0 | 21-33-11 | M00779 | E2 | 1A | | SM00017 | | W | | ALL |
| 155 | 22 | PA | | | 2-0 | 21-33-11 | M00779 | E5 | 1A | | SM00017 | | W | | ALL |
| 156 | 22 | PA | | | 1-11 | 21-33-11 | D04285J | 40 | | | SM00017 | | W | | ALL |
| 157 | 24 | PV | GG | | 3-8 | 32-42-12 | D05107J | 11 | | | L00119 | 2 | 1A | | ALL |
| 157Z | | | GG | | 0-0 | 32-42-12 | D05107J | DED | | | L00119 | DED | | | ALL |
| 158R | 22 | PH | | | 1-9 | 26-11-11 | M00779 | A2 | 1A | | SM00020 | | W | | ALL |
| 159R | 22 | PH | | | 1-9 | 26-11-11 | M00779 | A5 | 1A | | SM00020 | | W | | ALL |
| 160R | 22 | PH | | | 1-7 | 26-11-11 | D04513J | 2 | | | SM00020 | | W | | ALL |
| 161 | 22 | PQ | GK | | 3-6 | 79-33-11 | L00475 | 2 | 1A | | D05107J | 13 | | | ALL |
| 161Z | | | GK | | 0-0 | 79-33-11 | L00475 | DED | | | D05107J | DED | | | ALL |
| 162 | 22 | PA | | | 2-2 | 79-33-11 | L00474 | 2 | 1A | | D04285J | 42 | | | ALL |
| 163 | 24 | PV | GM | | 2-8 | 33-16-11 | TS0281 | A1 | 1A | | D04513J | 11 | | | ALL |
| 163Z | | | GM | | 0-0 | 33-16-11 | TS0281 | DED | | | D04513J | DED | | | ALL |
| 164 | 24 | PV | GN | | 2-8 | 33-16-11 | TS0281 | A3 | 1A | | D04513J | 12 | | | ALL |
| 164Z | | | GN | | 0-0 | 33-16-11 | TS0281 | DED | | | D04513J | DED | | | ALL |
| 165 | 24 | PV | GO | | 2-8 | 33-16-11 | TS0281 | A2 | 1A | | D04513J | 13 | | | ALL |
| 165Z | | | GO | | 0-0 | 33-16-11 | TS0281 | DED | | | D04513J | DED | | | ALL |
| 166 | 24 | PK | | | 2-8 | 33-16-11 | TS0281 | G | B | | D04513J | 10 | | | ALL |
| 167 | 24 | PK | | | 2-4 | 33-16-11 | TS0281 | B1 | 1A | | D04285J | 47 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0010
 Page 26
 May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0013 | 286T0013 | | | P1-3 CAPT INSTR PNL-R (continued) | | | | | | | | | | | | |
| 168 | 24 | | PK | | 2-4 | 33-16-11 | TS0281 | B3 | 1A | | D04285J | 48 | | | ALL | |
| 169 | 24 | | PK | | 2-4 | 33-16-11 | TS0281 | B2 | 1A | | D04285J | 49 | | | ALL | |
| 177 | 24 | | PK | | 2-6 | 31-51-43 | L00716 | 2 | 1B | | D04285J | 18 | | | ALL | |
| 901 | 22 | | PA | | 3-0 | 33-16-13 | D04580P | 40 | | | D04285J | 50 | | | 150, 152-199, 275-299 | |
| 902 | 22 | | PA | | 3-0 | 33-16-13 | D04580P | 41 | | | D04285J | 51 | | | 150, 152-199, 275-299 | |
| 903 | 22 | | PA | | 3-0 | 33-16-13 | D04586P | 40 | | | D04285J | 52 | | | 150, 152-199, 275-299 | |
| 904 | 22 | | PA | | 3-0 | 33-16-13 | D04586P | 41 | | | D04285J | 53 | | | 150, 152-199, 275-299 | |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE | | | | | | | | | | | | |
| 001 | 22 | | PA | | 3-2 | 27-51-11 | D01836A | C03 | | | TB0176F | A105 | 2 | | ALL | |
| 002 | 22 | | PA | | 3-2 | 27-51-11 | D01836A | G03 | | | TB0176F | C105 | 2 | | ALL | |
| 003 | 22 | | PA | | 3-2 | 27-51-11 | D01836B | A11 | | | TB0176F | A002 | 2 | | ALL | |
| 004 | 22 | | PA | | 3-2 | 27-51-11 | D01836B | B11 | | | TB0176F | C002 | 2 | | ALL | |
| 005 | 24 | | PK | | 3-2 | 27-51-61 | D01836B | C12 | | | TB0176F | A003 | 2 | | ALL | |
| 006 | 24 | | PK | | 3-2 | 27-51-61 | D01836B | A12 | | | TB0176F | C003 | 2 | | ALL | |
| 007 | 24 | | PK | | 3-2 | 27-51-11 | D01836B | A09 | | | TB0176F | A004 | 2 | | ALL | |
| 008 | 24 | | PK | | 3-2 | 27-51-11 | D01836B | B09 | | | TB0176F | C004 | 2 | | ALL | |
| 009 | 24 | | PK | | 3-2 | 27-51-11 | D01836B | C09 | | | TB0176F | A005 | 2 | | ALL | |
| 010 | 24 | | PK | | 3-2 | 27-51-11 | D01836B | D09 | | | TB0176F | C005 | 2 | | ALL | |
| 011 | 24 | | PK | | 3-2 | 27-51-11 | D01836B | E09 | | | TB0176F | A006 | 2 | | ALL | |
| 012 | 24 | | PK | | 3-2 | 27-51-11 | D01836B | F09 | | | TB0176F | C006 | 2 | | ALL | |
| 013 | 24 | | PK | | 3-2 | 27-51-11 | D01836B | G09 | | | TB0176F | A007 | 2 | | ALL | |
| 014 | 24 | | PK | | 3-2 | 27-51-11 | D01836B | H09 | | | TB0176F | C007 | 2 | | ALL | |
| 015 | 22 | | PA | | 2-4 | 27-51-61 | D01836B | D12 | | | GDX0001 | A.. | 2 | | ALL | |
| 016 | 22 | | PA | | 2-4 | 27-51-61 | D01836B | B12 | | | GDX0001 | A.. | 2 | | ALL | |
| 017 | 22 | | PA | | 2-4 | 27-51-61 | D01836B | J01 | | | GDX0001 | A.. | 2 | | ALL | |
| 018 | 24 | | PK | | 2-10 | 27-51-31 | D08034P | 3 | | | D01836A | A03 | | | ALL | |
| 019 | 22 | | PQ | CG | 3-9 | 27-51-61 | TB0176F | C064 | 2 | | D01836A | D12 | | | 050-099, 150-199, 275-276, 278-299 | |
| 019 | 22 | | PQ | CG | 3-9 | 27-51-61 | TB0176F | C064 | 2 | | D01836A | C07 | | | 277 | |
| 019Z | | | | CG | 0-0 | 27-51-61 | TB0176F | DED | | | D01836A | DED | | | ALL | |
| 020 | 24 | | PK | | 3-7 | 27-51-61 | TB0176G | 157 | 2 | | D01836B | H01 | | | 050-099 | |
| 020 | 24 | | PK | | 3-7 | 27-51-61 | TB0176G | 157 | 2 | | D01836B | H04 | | | 150-199, 275-299 | |
| 021 | 24 | | PK | | 2-9 | 27-51-61 | M02188 | A | D | | D01836B | K01 | | | ALL | |
| 022 | 24 | | PK | | 3-5 | 27-88-11 | D05626P | 6 | | | D01836B | A03 | | | ALL | |
| 023 | 24 | | PK | | 2-9 | 27-88-11 | D08034P | 19 | | | D01836B | B02 | | | ALL | |
| 024 | 24 | | PK | | 4-3 | 27-88-11 | TB0176G | 77 | 2 | | D01836B | F02 | | | ALL | |
| 025 | 24 | | PK | | 2-5 | 27-88-11 | D01836A | C08 | | | D01836B | A07 | | | 050-099 | |
| 025 | 24 | | PK | | 2-2 | 27-88-11 | D01836A | C08 | | | D01836B | A07 | | | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 27

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 026 | 24 | | PK | | 2-5 | 27-88-11 | D01836A | D08 | | | D01836B | B07 | | | 050-099 |
| 026 | 24 | | PK | | 2-2 | 27-88-11 | D01836A | D08 | | | D01836B | B07 | | | 150-199, 275-299 |
| 027 | 24 | | PK | | 4-5 | 27-88-11 | TB0176G | 77 | 2 | | D01836A | D04 | | | ALL |
| 028 | 22 | | PA | | 2-5 | 27-51-61 | D01836A | A06 | | | GDX0001 | D.. | 2 | | ALL |
| 029 | 22 | | PA | | 2-4 | 27-51-61 | D01836B | K02 | | | GDX0001 | A.. | 2 | | ALL |
| 030 | 24 | | PK | | 4-1 | 27-58-31 | D01836B | B03 | | | TB0176G | 68 | 2 | | ALL |
| 031 | 24 | | PK | | 3-3 | 27-51-41 | D05202P | 3 | | | TB0176G | 10 | 2 | | ALL |
| 032 | 24 | | PK | | 3-3 | 24-51-71 | D04110P | 31 | | | TB0176F | C059 | 2 | | ALL |
| 033 | 24 | | PK | | 3-1 | 27-51-41 | D01836A | C04 | | | TB0176G | 10 | 2 | | ALL |
| 034 | 24 | | PK | | 4-0 | 27-51-61 | D08034P | 5 | | | TB0176G | 157 | 2 | | ALL |
| 035 | 22 | | PQ | CH | 2-5 | 27-51-61 | D01836A | C12 | | | GDX0001 | A.. | 2 | | 050-099, 150-199, 275-276, 278-299 |
| 035 | 22 | | PQ | CH | 2-5 | 27-51-61 | D01836A | D07 | | | GDX0001 | A.. | 2 | | 277 |
| 035Z | | | | CH | 0-0 | 27-51-61 | D01836A | DED | | | GDX0001 | DED | | | ALL |
| 036 | 22 | | PA | | 2-5 | 27-51-61 | D01836A | K15 | | | GDX0001 | S.. | 2 | | ALL |
| 037 | 22 | | PQ | CI | 2-5 | 27-51-61 | D01836A | A12 | | | GDX0001 | A.. | 2 | | 050-099, 150-199, 275-276, 278-299 |
| 037 | 22 | | PQ | CI | 2-5 | 27-51-61 | D01836A | B07 | | | GDX0001 | A.. | 2 | | 277 |
| 037Z | | | | CI | 0-0 | 27-51-61 | D01836A | DED | | | GDX0001 | DED | | | ALL |
| 038 | 22 | | PA | | 2-5 | 27-51-61 | D01836A | B06 | | | GDX0001 | D.. | 2 | | ALL |
| 039 | 24 | | PK | | 2-11 | 27-58-31 | TB0176G | 10 | 2 | | D01836B | G02 | | | ALL |
| 040 | 24 | | PK | | 4-0 | 27-88-11 | D05626P | 51 | | | TB0176G | 77 | 2 | | ALL |
| 041 | 24 | | PK | | 2-4 | 27-58-11 | D01836B | H02 | | | D01836B | H08 | | | 050-099 |
| 041 | 24 | | PK | | 2-0 | 27-58-11 | D01836B | H02 | | | D01836B | H08 | | | 150-199, 275-299 |
| 042 | 24 | | PK | | 3-2 | 29-11-22 | D05212P | 1 | | | D04110P | 8 | | | ALL |
| 043 | 24 | | PK | | 3-9 | 27-51-51 | D08034P | 32 | | | TB0176G | 148 | 2 | | ALL |
| 044 | 24 | | PV | CJ | 4-3 | 27-51-61 | TB0176F | C073 | 2 | | D01836A | B12 | | | 050-099, 150-199, 275-276, 278-299 |
| 044 | 24 | | PV | CJ | 4-3 | 27-51-61 | TB0176F | C073 | 2 | | D01836A | A07 | | | 277 |
| 044Z | | | | CJ | 0-0 | 27-51-61 | TB0176F | DED | | | D01836A | DED | | | ALL |
| 045 | 24 | | PK | | 2-10 | 27-81-21 | D01836A | A02 | | | D08034P | 24 | | | ALL |
| 046 | 24 | | PK | | 2-10 | 27-81-11 | D08034P | 25 | | | D01836A | K01 | | | ALL |
| 047 | 22 | | PA | | 3-1 | 27-51-61 | D01836B | K07 | | | GDX0008 | A.. | 2 | | ALL |
| 048 | 24 | | PK | | 2-9 | 27-58-11 | D08034P | 34 | | | D01836B | G08 | | | ALL |
| 049 | 22 | | PA | | 3-2 | 27-81-11 | D01836A | D03 | | | TB0176F | A106 | 2 | | ALL |
| 050 | 22 | | PA | | 3-2 | 27-81-11 | D01836A | H03 | | | TB0176F | C106 | 2 | | ALL |
| 051 | 22 | | PA | | 2-11 | 27-81-11 | D01836B | C11 | | | TB0176F | C009 | 2 | | 050-099 |
| 051 | 22 | | PA | | 3-2 | 27-81-11 | D01836B | C11 | | | TB0176F | C009 | 2 | | 150-199, 275-299 |
| 052 | 22 | | PA | | 2-11 | 27-81-11 | D01836B | D11 | | | TB0176F | A013 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 28

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 053 | 22 | PA | | 2-9 | 27-81-21 | D01836B | F11 | | | | | TB0176F | A017 | 2 | ALL |
| 054 | 22 | PA | | 2-9 | 27-81-21 | D01836B | E11 | | | | | TB0176F | C017 | 2 | ALL |
| 055 | 22 | PA | | 5-3 | 27-81-21 | D01836A | E03 | | | | | TB0176F | A097 | 2 | ALL |
| 056 | 22 | PA | | 5-3 | 27-81-21 | D01836A | J03 | | | | | TB0176F | C097 | 2 | ALL |
| 057 | 24 | PK | | 3-7 | 27-81-31 | D05626P | 5 | | | | | D01836A | B03 | | ALL |
| 058 | 24 | PK | | 3-5 | 27-51-61 | D01836B | K12 | | | | | D05288P | 8 | | ALL |
| 059 | 24 | PK | | 3-9 | 27-51-11 | D05626P | 7 | | | | | TB0176G | 22 | 2 | ALL |
| 060 | 24 | PK | | 4-0 | 27-81-11 | D05626P | 3 | | | | | TB0176F | A080 | 2 | ALL |
| 061 | 22 | PA | | 3-5 | 27-58-31 | D05626P | 4 | | | | | D01836B | C03 | | ALL |
| 062 | 24 | PK | | 3-5 | 27-88-11 | D05626P | 30 | | | | | D01836B | D03 | | ALL |
| 063 | 24 | PK | | 3-5 | 27-88-11 | D05626P | 31 | | | | | D01836B | F03 | | ALL |
| 064 | 24 | PK | | 3-1 | 27-88-11 | TB0176G | 136 | 2 | | | | D01836B | E03 | | ALL |
| 065 | 24 | PK | | 3-7 | 27-88-11 | D05626P | 33 | | | | | D01836A | B04 | | ALL |
| 066 | 24 | PK | | 3-7 | 27-88-11 | D05626P | 34 | | | | | D01836A | K03 | | ALL |
| 067 | 24 | PK | | 3-7 | 27-88-11 | D05626P | 35 | | | | | D01836A | A04 | | ALL |
| 069 | 24 | PK | | 2-9 | 29-11-32 | D01836B | H03 | | | | | TB0176F | A021 | 2 | ALL |
| 070 | 24 | PK | | 3-3 | 27-51-61 | TB0176G | 157 | 2 | | | | D05288P | 7 | | ALL |
| 071 | 20 | UA | | 1-6 | 21-31-21 | D02712A | | | | FD | | GDX0012 | S.. | 2 | ALL |
| 072 | 20 | UA | | 1-6 | 21-31-21 | D02712A | | | | FE | | GDX0012 | S.. | 2 | ALL |
| 073 | 24 | PK | | 4-8 | 21-31-21 | D08034P | 41 | | | | | D02712A | D02 | | ALL |
| 074 | 24 | PK | | 4-8 | 21-31-21 | D08034P | 42 | | | | | D02712A | A02 | | ALL |
| 075 | 22 | PQ | CC | 4-8 | 21-31-21 | D08034P | 43 | | | | | D02712A | A15 | | ALL |
| 075Z | | | CC | 0-0 | 21-31-21 | D08034P | DED | | | | | D02712A | DED | | ALL |
| 076 | 22 | PA | | 2-3 | 21-31-21 | D02712A | D15 | | | | | GDX0012 | A.. | 2 | ALL |
| 077 | 24 | PK | | 4-4 | 21-31-21 | D05212P | 9 | | | | | D02712A | B02 | | ALL |
| 078 | 24 | PK | | 4-10 | 21-31-21 | TB0176D | A116 | 2 | | | | D02712A | B08 | | ALL |
| 079 | 22 | PA | | 2-3 | 21-31-21 | D02712A | B12 | | | | | GDX0012 | S.. | 2 | ALL |
| 080 | 24 | PK | | 3-9 | 27-51-61 | TB0176G | 74 | 2 | | | | D05288P | 9 | | 050-099 |
| 081 | 24 | PK | | 3-7 | 24-22-12 | D04110P | 1 | | | | | TB0176F | C027 | 2 | ALL |
| 082 | 24 | PK | | 3-7 | 24-22-12 | D04110P | 2 | | | | | TB0176F | A028 | 2 | ALL |
| 083 | 24 | PK | | 3-7 | 24-27-21 | D04110P | 15 | | | | | TB0176F | A024 | 2 | ALL |
| 084 | 24 | PK | | 2-11 | 24-27-21 | D04110P | 16 | | | | | TB0176F | A030 | 2 | ALL |
| 086 | 22 | PA | | 2-11 | 25-31-21 | D04110P | 5 | | | | | TB0176G | 171 | 2 | 050-099 |
| 086 | 22 | PA | | 3-7 | 25-31-21 | D04110P | 5 | | | | | TB0176G | 171 | 2 | 150-199, 275-278 |
| 086 | 22 | PA | | 2-11 | 25-31-21 | D04110P | 5 | | | | | TB0176F | C036 | 2 | 280-299 |
| 087 | 22 | PA | | 2-11 | 25-31-21 | D04110P | 7 | | | | | TB0176G | 172 | 2 | 050-099 |
| 087 | 22 | PA | | 3-7 | 25-31-21 | D04110P | 7 | | | | | TB0176G | 172 | 2 | 150-199 |
| 088 | 24 | PK | | 3-3 | 24-51-71 | D04110P | 19 | | | | | TB0176F | A060 | 2 | ALL |
| 089 | 22 | PA | | 4-0 | 29-33-11 | D02704B | A09 | | | | | TB0176F | A156 | 2 | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 29

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 105 | 22 | | PA | | 4-0 | 29-33-11 | D02704B | A08 | | | TB0176F | C156 | 2 | | ALL |
| 107 | 24 | | PK | | 4-1 | 27-51-61 | TB0176G | 74 | 2 | | D01836B | F06 | | | 050-099 |
| 108 | 24 | | PK | | 4-1 | 27-51-61 | TB0176G | 74 | 2 | | D01836B | F08 | | | 050-099 |
| 109 | 24 | | PK | | 2-11 | 24-51-71 | D04960P | 3 | | | TB0176F | C040 | 2 | | ALL |
| 110 | 24 | | PK | | 3-4 | 24-51-71 | D04960P | 4 | | | TB0176F | A060 | 2 | | ALL |
| 111 | 22 | | PA | | 3-5 | 27-88-11 | D01836B | G03 | | | D05626P | | 1 | | ALL |
| 112 | 22 | | PA | | 4-1 | 29-33-11 | D02704A | A06 | | | TB0176G | 154 | 2 | | ALL |
| 113 | 24 | | PK | | 4-2 | 29-33-11 | D05734P | 13 | | | TB0176G | 155 | 2 | | ALL |
| 114 | 22 | | PA | | 4-1 | 29-33-11 | D02704A | A15 | | | TB0176G | 155 | 2 | | ALL |
| 115 | 24 | | PK | | 4-2 | 29-33-11 | D05734P | 8 | | | TB0176G | 154 | 2 | | ALL |
| 116 | 24 | | PK | | 3-2 | 29-11-22 | D04110P | 18 | | | D05212P | 5 | | | ALL |
| 117 | 24 | | PK | | 2-11 | 24-51-71 | D04110P | 35 | | | TB0176F | C040 | 2 | | ALL |
| 118 | 22 | | PA | | 2-2 | 33-24-11 | D01836B | B04 | | | GDX0002 | D.. | 2 | | ALL |
| 119 | 24 | | PK | | 4-1 | 33-24-11 | D01836B | A04 | | | TB0176F | A075 | 2 | | ALL |
| 122 | 18 | | PA | | 3-4 | 77-31-11 | D02708C | 4 | | | GDX0002 | A.. | 2 | | ALL |
| 123 | 20 | | UA | | 4-0 | 77-31-11 | D02708B | | | FG | GDX0002 | S.. | 2 | | 050-099 |
| 123 | 20 | | UA | | 3-5 | 77-31-11 | D02708B | | | FG | GDX0002 | S.. | 2 | | 150-199, 275-299 |
| 124 | 22 | | PA | | 3-7 | 25-31-21 | D04110P | 7 | | | TB0176G | 172 | 2 | | 275-278 |
| 124 | 22 | | PA | | 3-7 | 25-31-21 | D04110P | 7 | | | TB0176F | A172 | 2 | | 280-299 |
| 125 | 18 | | PA | | 3-4 | 77-31-11 | D02708C | 3 | | | GDX0002 | S.. | 2 | | ALL |
| 126 | 22 | | PA | | 4-0 | 77-31-11 | D02708B | A15 | | | GDX0002 | D.. | 2 | | 050-099 |
| 126 | 22 | | PA | | 3-5 | 77-31-11 | D02708B | A15 | | | GDX0002 | D.. | 2 | | 150-199, 275-299 |
| 127 | 20 | | UA | | 3-7 | 77-31-11 | D02708A | | | FH | GDX0002 | S.. | 2 | | ALL |
| 128 | 24 | | PK | | 4-3 | 27-51-61 | TB0176G | 74 | 2 | | D01836A | B08 | | | 050-099 |
| 130 | 24 | | PK | | 2-6 | 29-33-11 | D02704B | A01 | | | TB0176G | 117 | 2 | | ALL |
| 133 | 22 | | PA | | 2-0 | 29-33-11 | D02704B | A12 | | | GDZ0001 | S.. | E | *4 | ALL |
| 135 | 24 | | PK | | 3-3 | 29-33-11 | D02704A | A14 | | | D05734P | 9 | | | ALL |
| 137 | 22 | | PA | | 2-0 | 29-33-11 | D02704B | B11 | | | GDX0002 | A.. | 2 | | ALL |
| 139 | 24 | | PK | | 3-3 | 29-33-11 | D02704A | A05 | | | D05734P | 12 | | | ALL |
| 141 | 22 | | PA | | 2-1 | 29-33-11 | D02704A | B08 | | | GDX0002 | A.. | 2 | | ALL |
| 142 | 22 | | PA | | 2-0 | 29-33-11 | D02704B | A15 | | | GDX0002 | S.. | 2 | | ALL |
| 146 | 24 | | PK | | 4-8 | 29-33-11 | D02704B | C07 | | | TB0176F | A082 | 2 | | ALL |
| 147 | 24 | | PK | | 4-8 | 29-33-11 | D02704B | A07 | | | TB0176F | C082 | 2 | | ALL |
| 148 | 24 | | PK | | 4-8 | 29-33-11 | D02704B | B07 | | | TB0176F | A083 | 2 | | ALL |
| 149 | 24 | | PV | AZ | 3-3 | 29-33-11 | D02704A | B11 | | | D05734P | 17 | | | ALL |
| 149Z | | | | AZ | 0-0 | 29-33-11 | D02704A | REF | | FO | D05734P | REF | | FW | ALL |
| 150 | 24 | | PK | | 3-3 | 29-33-11 | D02704A | C13 | | | D05734P | 3 | | | ALL |
| 151 | 24 | | PK | | 3-3 | 29-33-11 | D02704A | A13 | | | D05734P | 4 | | | ALL |
| 152 | 24 | | PK | | 3-3 | 29-33-11 | D02704A | B13 | | | D05734P | 5 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0010
Page 30
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 153 | 24 | PV | BA | 3-6 | 29-33-11 | D02704A | B02 | | | | D05364P | 11 | | | ALL |
| 153Z | | | BA | 0-0 | 29-33-11 | D02704A | REF | | FP | | D05364P | REF | | FT | ALL |
| 154 | 24 | PK | | 3-6 | 29-33-11 | D02704A | C04 | | | | D05364P | 3 | | | ALL |
| 155 | 24 | PK | | 3-6 | 29-33-11 | D02704A | A04 | | | | D05364P | 4 | | | ALL |
| 156 | 24 | PK | | 3-6 | 29-33-11 | D02704A | B04 | | | | D05364P | 5 | | | ALL |
| 157 | 24 | PK | | 4-2 | 29-33-11 | D02704B | A14 | | | | D05212P | 2 | | | ALL |
| 158 | 24 | PK | | 4-4 | 29-33-11 | D02704A | C14 | | | | D05212P | 6 | | | ALL |
| 159 | 24 | PK | | 4-2 | 29-33-11 | D02704B | C08 | | | | D05212P | 7 | | | ALL |
| 160 | 24 | PK | | 4-4 | 29-33-11 | D02704A | C05 | | | | D05212P | 8 | | | ALL |
| 161 | 24 | PK | | 3-9 | 28-41-13 | D05202P | 19 | | | | TB0176F | A146 | 2 | | ALL |
| 162 | 24 | PK | | 3-11 | 24-27-11 | D04110P | 17 | | | | TB0176F | C084 | 2 | | ALL |
| 163 | 20 | UA | | 2-4 | 27-51-51 | D01836A | | | FJ | | GD00002 | S.. | 2 | | ALL |
| 166 | 22 | PA | | 2-0 | 27-51-61 | D01836B | G11 | | | | GD00003 | D.. | 2 | | ALL |
| 167 | 24 | PK | | 4-3 | 27-32-11 | D01836A | F04 | | | | TB0176F | A069 | 2 | | ALL |
| 168 | 24 | PK | | 4-3 | 27-32-11 | D01836A | G04 | | | | TB0176F | C069 | 2 | | ALL |
| 169 | 24 | PK | | 3-9 | 27-32-11 | D01836A | H04 | | | | TB0176F | C050 | 2 | | ALL |
| 170 | 24 | PK | | 3-0 | 27-32-11 | D01836A | J04 | | | | TB0176F | C110 | 2 | | ALL |
| 171 | 24 | PK | | 2-10 | 27-32-21 | D01836B | A08 | | | | TB0176F | A113 | 2 | | ALL |
| 172 | 24 | PK | | 2-10 | 27-32-21 | D01836B | B08 | | | | TB0176F | C113 | 2 | | ALL |
| 173 | 24 | PK | | 2-10 | 27-32-21 | D01836B | C08 | | | | TB0176F | A114 | 2 | | ALL |
| 174 | 24 | PK | | 2-10 | 27-32-21 | D01836B | D08 | | | | TB0176F | C114 | 2 | | ALL |
| 175 | 22 | PA | | 2-3 | 21-31-21 | D02712A | C12 | | | | GD00012 | D.. | 2 | | ALL |
| 176 | 24 | PK | | 2-8 | 29-33-11 | D02704A | A08 | | | | TB0176G | 117 | 2 | | ALL |
| 177 | 24 | PK | | 2-6 | 29-33-11 | D02704B | A11 | | | | TB0176G | 117 | 2 | | ALL |
| 178 | 22 | PA | | 2-3 | 29-33-11 | D02704B | A13 | | | | GD00001 | S.. | E | *4 | ALL |
| 180 | 22 | PA | | 2-3 | 29-33-11 | D02704B | B01 | | | | GD00003 | A.. | 2 | | ALL |
| 183 | 24 | PK | | 3-11 | 24-22-11 | D04110P | 20 | | | | TB0176F | A079 | 2 | | ALL |
| 184 | 20 | PA | | 3-9 | 24-22-12 | D04110P | 22 | | | | TB0176F | A118 | 2 | | ALL |
| 185 | 24 | PK | | 3-9 | 24-51-31 | D04110P | 23 | | | | TB0176F | C118 | 2 | | ALL |
| 186 | 24 | PK | | 3-9 | 24-22-12 | D04110P | 24 | | | | TB0176F | A119 | 2 | | ALL |
| 187 | 24 | PK | | 3-9 | 24-51-31 | D04110P | 25 | | | | TB0176F | C119 | 2 | | ALL |
| 188 | 20 | PA | | 3-9 | 24-22-12 | D04110P | 26 | | | | TB0176F | A120 | 2 | | ALL |
| 189 | 24 | PK | | 3-9 | 24-22-12 | D04110P | 30 | | | | TB0176F | C120 | 2 | | ALL |
| 190 | 20 | PA | | 4-1 | 24-22-22 | D04110P | 29 | | | | TB0176F | A101 | 2 | | ALL |
| 191 | 24 | PK | | 4-1 | 24-51-31 | D04110P | 27 | | | | TB0176F | C101 | 2 | | ALL |
| 192 | 20 | PA | | 4-1 | 24-22-22 | D04110P | 28 | | | | TB0176F | A102 | 2 | | ALL |
| 193 | 24 | PK | | 4-1 | 24-51-31 | D04110P | 21 | | | | TB0176F | C102 | 2 | | ALL |
| 194 | 24 | PK | | 2-4 | 21-31-21 | D02712A | D05 | | | | D02712A | C06 | | | ALL |
| 197 | 22 | PA | | 4-0 | 28-41-13 | D08024P | 35 | | | | TB0176F | C146 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 31

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|----------|---------|---------|-------|------|------|---------|-------|------|------|--------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 198 | 24 | PV | AT | 4-1 | 29-11-31 | D04110P | | 32 | | | TB0176F | A107 | 2 | | ALL |
| 198Z | | | AT | 0-0 | 29-11-31 | D04110P | | DED | | | TB0176F | DED | | | ALL |
| 199 | 24 | PV | AX | 4-1 | 29-11-31 | D04110P | | 33 | | | TB0176F | C107 | 2 | | ALL |
| 199Z | | | AX | 0-0 | 29-11-31 | D04110P | | DED | | | TB0176F | DED | | | ALL |
| 201B | 24 | PL | A | 3-2 | 27-51-11 | D01836B | | J09 | | | TB0176F | A008 | 2 | | ALL |
| 201R | 24 | PL | A | 0-0 | 27-51-11 | D01836B | | K09 | | | TB0176F | C008 | 2 | | ALL |
| 202B | 22 | PB | B | 2-10 | 27-51-31 | D08034P | | 8 | | | D01836A | A09 | | | ALL |
| 202R | 22 | PB | B | 0-0 | 27-51-31 | D08034P | | 9 | | | D01836A | B09 | | | ALL |
| 203B | 24 | PL | D | 2-10 | 27-51-31 | D08034P | | 28 | | | D01836A | B01 | | | ALL |
| 203R | 24 | PL | D | 0-0 | 27-51-31 | D08034P | | 29 | | | D01836A | A01 | | | ALL |
| 204B | 24 | PL | E | 2-9 | 27-58-31 | D08034P | | 30 | | | D01836B | B01 | | | ALL |
| 204R | 24 | PL | E | 0-0 | 27-58-31 | D08034P | | 31 | | | D01836B | A01 | | | ALL |
| 205B | 22 | PB | F | 3-7 | 27-51-41 | D05626P | | 20 | | | D01836A | D11 | | | ALL |
| 205R | 22 | PB | F | 0-0 | 27-51-41 | D05626P | | 21 | | | D01836A | C11 | | | ALL |
| 208B | 22 | PB | I | 3-7 | 27-51-41 | D05626P | | 9 | | | D01836A | D14 | | | ALL |
| 208R | 22 | PB | I | 0-0 | 27-51-41 | D05626P | | 10 | | | D01836A | C14 | | | ALL |
| 209B | 22 | PB | J | 3-1 | 27-51-41 | D08024P | | 1 | | | D01836A | H09 | | | ALL |
| 209R | 22 | PB | J | 0-0 | 27-51-41 | D08024P | | 2 | | | D01836A | G09 | | | ALL |
| 212B | 22 | PB | M | 3-1 | 27-51-41 | D08024P | | 24 | | | D01836A | D10 | | | ALL |
| 212R | 22 | PB | M | 0-0 | 27-51-41 | D08024P | | 25 | | | D01836A | C10 | | | ALL |
| 213B | 24 | PL | V | 2-9 | 27-58-31 | D08034P | | 13 | | | D01836B | F01 | | | ALL |
| 213R | 24 | PL | V | 0-0 | 27-58-31 | D08034P | | 14 | | | D01836B | G01 | | | ALL |
| 214B | 24 | PL | Y | 2-11 | 27-81-11 | D01836B | | B10 | | | TB0176F | A014 | 2 | | ALL |
| 214R | 24 | PL | Y | 0-0 | 27-81-11 | D01836B | | A10 | | | TB0176F | C013 | 2 | | ALL |
| 215B | 24 | PL | Z | 2-9 | 27-81-21 | D01836B | | C10 | | | TB0176F | A018 | 2 | | ALL |
| 215R | 24 | PL | Z | 0-0 | 27-81-21 | D01836B | | D10 | | | TB0176F | C018 | 2 | | ALL |
| 216B | 22 | PB | AB | 3-1 | 27-81-31 | D08024P | | 19 | | | D01836A | C09 | | | ALL |
| 216R | 22 | PB | AB | 0-0 | 27-81-31 | D08024P | | 20 | | | D01836A | D09 | | | ALL |
| 217B | 22 | PB | AD | 3-7 | 27-81-31 | D05626P | | 15 | | | D01836A | E09 | | | ALL |
| 217R | 22 | PB | AD | 0-0 | 27-81-31 | D05626P | | 16 | | | D01836A | F09 | | | ALL |
| 218B | 24 | PW | AF | 2-8 | 21-31-21 | D02712A | | A05 | | | TB0176G | 85 | 2 | | ALL |
| 218R | 24 | PW | AF | 0-0 | 21-31-21 | D02712A | | B06 | | | TB0176G | 86 | 2 | | ALL |
| 218Z | | | AF | 0-0 | 21-31-21 | D02712A | | | | FD | TB0176F | A087 | 2 | | ALL |
| 219B | 24 | PW | AG | 4-5 | 21-31-21 | D02712A | | C05 | | | TB0176G | 124 | 2 | | ALL |
| 219R | 24 | PW | AG | 0-0 | 21-31-21 | D02712A | | D06 | | | TB0176G | 125 | 2 | | ALL |
| 219Z | | | AG | 0-0 | 21-31-21 | D02712A | | | | FD | TB0176G | 126 | 2 | | ALL |
| 220B | 24 | PL | AJ | 4-4 | 21-31-21 | D02712A | | C03 | | | D05212P | 10 | | | ALL |
| 220R | 24 | PL | AJ | 0-0 | 21-31-21 | D02712A | | C04 | | | D05212P | 11 | | | ALL |
| 221B | 24 | PL | AK | 4-4 | 21-31-21 | D02712A | | D03 | | | D05212P | 12 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0010
 Page 32
 May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|----------|-------|---------|-------|------|------|---------|-------|------|------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 221R | 24 | PL | AK | 0-0 | 21-31-21 | | D02712A | D04 | | | D05212P | 13 | | | ALL |
| 222B | 24 | PL | AL | 4-5 | 21-31-21 | | D02712A | A08 | | | TB0176F | A129 | 2 | | 050-099 |
| 222B | 24 | PL | AL | 3-9 | 21-31-21 | | D02712A | A08 | | | TB0176F | A129 | 2 | | 150-199, 275-299 |
| 222R | 24 | PL | AL | 0-0 | 21-31-21 | | D02712A | A07 | | | TB0176F | C129 | 2 | | ALL |
| 223B | 24 | PW | AI | 4-6 | 21-31-21 | | D02712A | B11 | | | TB0176F | C024 | 2 | | ALL |
| 223R | 24 | PW | AI | 0-0 | 21-31-21 | | D02712A | C11 | | | TB0176F | A025 | 2 | | ALL |
| 223Z | | | AI | 0-0 | 21-31-21 | | D02712A | | | FE | TB0176F | C025 | 2 | | ALL |
| 224B | 22 | PR | AR | 3-5 | 29-11-31 | | D04110P | | 13 | | D05288P | 5 | | | ALL |
| 224R | 22 | PR | AR | 0-0 | 29-11-31 | | D04110P | | 14 | | D05288P | 6 | | | ALL |
| 224Z | | | AR | 0-0 | 29-11-31 | | D04110P | | DED | | D05288P | DED | | | ALL |
| 225B | 24 | PL | AN | 3-11 | 21-31-21 | | D02712A | A11 | | | D04960P | 8 | | | ALL |
| 225R | 24 | PL | AN | 0-0 | 21-31-21 | | D02712A | A10 | | | D04960P | 9 | | | ALL |
| 226B | 24 | PW | AO | 2-9 | 24-22-12 | | D04110P | | 10 | | TB0176F | A134 | 2 | | ALL |
| 226R | 24 | PW | AO | 0-0 | 24-22-12 | | D04110P | | 11 | | TB0176F | C134 | 2 | | ALL |
| 226Z | | | AO | 0-0 | 24-22-12 | | D04110P | | 12 | | TB0176F | A135 | 2 | | ALL |
| 231B | 24 | PW | AU | 5-0 | 77-31-11 | | D05202P | 8 | | | D02708A | C06 | | | 050-099 |
| 231B | 24 | PW | AU | 4-1 | 77-31-11 | | D05202P | 8 | | | D02708A | C06 | | | 150-199, 275-299 |
| 231R | 24 | PW | AU | 0-0 | 77-31-11 | | D05202P | 7 | | | D02708A | D06 | | | ALL |
| 231Z | | | AU | 0-0 | 77-31-11 | | D05202P | 9 | | | D02708A | REF | | FX | 050-099 |
| 231Z | | | AU | 0-0 | 77-31-11 | | D05202P | 9 | | | D02708A | | | FX | 150-199, 275-299 |
| 232B | 22 | PR | AV | 5-0 | 77-31-11 | | D08034P | 51 | | | D02708A | B01 | | | 050-099 |
| 232B | 22 | PR | AV | 4-1 | 77-31-11 | | D08034P | 51 | | | D02708A | B01 | | | 150-199, 275-299 |
| 232R | 22 | PR | AV | 0-0 | 77-31-11 | | D08034P | 50 | | | D02708A | A01 | | | ALL |
| 232Z | | | AV | 0-0 | 77-31-11 | | D08034P | 52 | | | D02708A | | | FH | ALL |
| 233B | 22 | PR | AW | 2-10 | 77-31-11 | | D02708B | B01 | | | TB0176F | C076 | 2 | | ALL |
| 233R | 22 | PR | AW | 0-0 | 77-31-11 | | D02708B | A01 | | | TB0176F | A076 | 2 | | ALL |
| 233Z | | | AW | 0-0 | 77-31-11 | | D02708B | | | FG | TB0176F | C075 | 2 | | ALL |
| 234B | 24 | PW | BB | 2-7 | 27-51-51 | | TB0176G | | 124 | 2 | D01836A | F01 | | | ALL |
| 234R | 24 | PW | BB | 0-0 | 27-51-51 | | TB0176G | | 125 | 2 | D01836A | E01 | | | ALL |
| 234Z | | | BB | 0-0 | 27-51-51 | | TB0176G | | 126 | 2 | D01836A | | | FJ | ALL |
| 235B | 24 | PW | BC | 4-5 | 27-51-51 | | TB0176G | | 85 | 2 | D01836A | H05 | | | 050-099 |
| 235B | 24 | PW | BC | 4-2 | 27-51-51 | | TB0176G | | 85 | 2 | D01836A | H05 | | | 150-199, 275-299 |
| 235R | 24 | PW | BC | 0-0 | 27-51-51 | | TB0176G | | 86 | 2 | D01836A | G05 | | | ALL |
| 235Z | | | BC | 0-0 | 27-51-51 | | GDY0013 | S.. | 2 | | D01836A | | | FJ | 050-099, 162-199, 277-299 |
| 235Z | | | BC | 0-0 | 27-51-51 | | GDY0011 | S.. | 2 | | D01836A | | | FJ | 150-157, 275-276 |
| 236B | 24 | PL | DL | 4-0 | 28-41-13 | | D08024P | | 37 | | TB0176F | C147 | 2 | | ALL |
| 236R | 24 | PL | DL | 0-0 | 28-41-13 | | D08024P | | 36 | | TB0176F | A147 | 2 | | ALL |
| 240B | 24 | PW | BJ | 2-5 | 27-51-51 | | D05705P | | 4 | | TB0176G | 124 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 33

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 240R | 24 | PW | BJ | | 0-0 | 27-51-51 | D05705P | | 3 | | | TB0176G | 125 | 2 | | ALL |
| 240Z | | | BJ | | 0-0 | 27-51-51 | D05705P | | 5 | | | TB0176G | 126 | 2 | | ALL |
| 241B | 24 | PW | BK | | 2-5 | 34-61-14 | D05705P | | 17 | | | TB0176F | C127 | 2 | | ALL |
| 241R | 24 | PW | BK | | 0-0 | 34-61-14 | D05705P | | 16 | | | TB0176F | A127 | 2 | | ALL |
| 241Z | | | BK | | 0-0 | 34-61-14 | D05705P | | 18 | | | TB0176F | A026 | 2 | | ALL |
| 242B | 24 | PW | BN | | 4-0 | 73-21-14 | D08034P | | 44 | | | TB0176G | 160 | 2 | | ALL |
| 242R | 24 | PW | BN | | 0-0 | 73-21-14 | D08034P | | 45 | | | TB0176G | 161 | 2 | | ALL |
| 242Z | | | BN | | 0-0 | 73-21-14 | D08034P | | | | FQ | TB0176G | 159 | 2 | | ALL |
| 243B | 24 | PW | BO | | 4-5 | 73-21-14 | D08034P | | 46 | | | TB0176G | 168 | 2 | | ALL |
| 243R | 24 | PW | BO | | 0-0 | 73-21-14 | D08034P | | 47 | | | TB0176G | 169 | 2 | | ALL |
| 243Z | | | BO | | 0-0 | 73-21-14 | D08034P | | | | FQ | TB0176G | 170 | 2 | | 050-099, 153-199, 275-299 |
| 243Z | | | BO | | 0-0 | 73-21-14 | D08034P | | | | FQ | TB0176F | A170 | 2 | | 150-152 |
| 244B | 24 | PW | BP | | 5-8 | 34-12-61 | D04331P | | 3 | | | TB0176G | 168 | 2 | | 050-099 |
| 244B | 24 | PW | BP | | 6-2 | 34-12-61 | D04331P | | 3 | | | TB0176G | 168 | 2 | | 150-199, 275-299 |
| 244R | 24 | PW | BP | | 0-0 | 34-12-61 | D04331P | | 4 | | | TB0176G | 169 | 2 | | ALL |
| 244Z | | | BP | | 0-0 | 34-12-61 | D04331P | | 5 | | | GDY0011 | S.. | 2 | | ALL |
| 247 | 20 | UA | | | 2-0 | 77-31-11 | D02708B | | | | FF | GDY0008 | S.. | 2 | | 050, 150-199, 275-299 |
| 247 | 20 | UA | | | 2-0 | 77-31-11 | D02708B | | | | FF | GDY0008 | S.. | 2 | * | 051-099 |
| 247B | 24 | PW | DD | | 2-9 | 77-31-11 | D02708B | | B08 | | | TB0176F | A142 | 2 | | ALL |
| 247R | 24 | PW | DD | | 0-0 | 77-31-11 | D02708B | | A08 | | | TB0176F | C141 | 2 | | ALL |
| 247Z | | | DD | | 0-0 | 77-31-11 | D02708B | | | | FF | TB0176F | C143 | 2 | | ALL |
| 248 | 20 | UA | | | 2-0 | 77-31-11 | D02708A | | | | FI | GDY0008 | S.. | 2 | | 050, 150-199, 275-299 |
| 248 | 20 | UA | | | 2-0 | 77-31-11 | D02708A | | | | FI | GDY0008 | S.. | 2 | * | 051-099 |
| 248B | 24 | PW | CF | | 5-0 | 77-31-11 | D02708A | | B08 | | | D08034P | 54 | | | 050-099 |
| 248B | 24 | PW | CF | | 4-1 | 77-31-11 | D02708A | | B08 | | | D08034P | 54 | | | 150-199, 275-299 |
| 248R | 24 | PW | CF | | 0-0 | 77-31-11 | D02708A | | A08 | | | D08034P | 53 | | | ALL |
| 248Z | | | CF | | 0-0 | 77-31-11 | D02708A | | | | FI | D08034P | 49 | | | ALL |
| 249B | 24 | PW | CD | | 2-9 | 77-31-11 | D02708B | | D10 | | | TB0176F | A143 | 2 | | ALL |
| 249R | 24 | PW | CD | | 0-0 | 77-31-11 | D02708B | | C10 | | | TB0176F | C142 | 2 | | ALL |
| 249Z | | | CD | | 0-0 | 77-31-11 | D02708B | | DED | | | TB0176F | A145 | 2 | | ALL |
| 250B | 24 | PW | CE | | 5-0 | 77-31-11 | D02708A | | D10 | | | D08034P | 27 | | | 050-099 |
| 250B | 24 | PW | CE | | 4-1 | 77-31-11 | D02708A | | D10 | | | D08034P | 27 | | | 150-199, 275-299 |
| 250R | 24 | PW | CE | | 0-0 | 77-31-11 | D02708A | | C10 | | | D08034P | 26 | | | ALL |
| 250Z | | | CE | | 0-0 | 77-31-11 | D02708A | | DED | | | D08034P | 2 | | | ALL |
| 251B | 22 | PR | AM | | 4-10 | 21-31-21 | D02712A | | B13 | | | TB0176F | A115 | 2 | | ALL |
| 251R | 22 | PR | AM | | 0-0 | 21-31-21 | D02712A | | C13 | | | TB0176F | C115 | 2 | | ALL |
| 251Z | | | AM | | 0-0 | 21-31-21 | D02712A | | DED | | | TB0176F | DED | | | ALL |
| 252B | 24 | PW | BG | | 2-5 | 31-31-19 | D01836A | | K02 | | | D05705P | 10 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0010
Page 34
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 252R | 24 | PW | BG | 0-0 | 31-31-19 | D01836A | J02 | | | D05705P | 9 | | | ALL | |
| 252Z | | | BG | 0-0 | 31-31-19 | D01836A | DED | | | D05705P | 11 | | | ALL | |
| 269B | 22 | PR | KS | 5-4 | 31-31-22 | D04331P | 19 | | | TB0176X | A058 | BJ | | ALL | |
| 269R | 22 | PR | KS | 0-0 | 31-31-22 | D04331P | 18 | | | TB0176X | A057 | BJ | | ALL | |
| 269Z | | | KS | 0-0 | 31-31-22 | D04331P | 20 | | | GDY0009 | S.. | 2 | | ALL | |
| 270B | 24 | PW | KT | 3-8 | 31-35-12 | TB0176G | 166 | 2 | | D05705P | 13 | | | ALL | |
| 270R | 24 | PW | KT | 0-0 | 31-35-12 | TB0176G | 165 | 2 | | D05705P | 12 | | | ALL | |
| 270Z | | | KT | 0-0 | 31-35-12 | GDY0010 | S.. | 2 | | D05705P | 14 | | | 050-099, 162-199, 277-299 | |
| 270Z | | | KT | 0-0 | 31-35-12 | GDY0009 | S.. | 2 | | D05705P | 14 | | | 150-157, 275-276 | |
| 271B | 24 | PW | KU | 3-8 | 31-35-12 | TB0176G | 175 | 2 | | D05705P | 20 | | | 050-099 | |
| 271B | 24 | PW | KU | 5-0 | 31-35-12 | TB0176G | 175 | 2 | | D05705P | 20 | | | 150-199, 275-299 | |
| 271R | 24 | PW | KU | 0-0 | 31-35-12 | TB0176G | 176 | 2 | | D05705P | 19 | | | ALL | |
| 271Z | | | KU | 0-0 | 31-35-12 | GDY0011 | S.. | 2 | | D05705P | 21 | | | ALL | |
| 272B | 24 | PW | KV | 3-8 | 31-35-12 | TB0176G | 173 | 2 | | D05705P | 23 | | | ALL | |
| 272R | 24 | PW | KV | 0-0 | 31-35-12 | TB0176G | 174 | 2 | | D05705P | 22 | | | ALL | |
| 272Z | | | KV | 0-0 | 31-35-12 | GDY0011 | S.. | 2 | | D05705P | 24 | | | ALL | |
| 273B | 24 | PW | KW | 5-8 | 28-41-11 | TB0176G | 166 | 2 | | D04331P | 24 | | | 050-099 | |
| 273B | 24 | PW | KW | 6-2 | 28-41-11 | TB0176G | 166 | 2 | | D04331P | 24 | | | 150-199, 275-299 | |
| 273R | 24 | PW | KW | 0-0 | 28-41-11 | TB0176G | 165 | 2 | | D04331P | 23 | | | ALL | |
| 273Z | | | KW | 0-0 | 28-41-11 | GDY0010 | S.. | 2 | | D04331P | 25 | | | 050-099, 162-199, 277-299 | |
| 273Z | | | KW | 0-0 | 28-41-11 | GDY0009 | S.. | 2 | | D04331P | 25 | | | 150-157, 275-276 | |
| 274B | 24 | PW | KX | 5-8 | 31-41-35 | TB0176F | A167 | 2 | | D04331P | 26 | | | ALL | |
| 274R | 24 | PW | KX | 0-0 | 31-41-35 | TB0176F | C167 | 2 | | D04331P | 27 | | | ALL | |
| 274Z | | | KX | 0-0 | 31-41-35 | GDY0010 | S.. | 2 | | D04331P | 28 | | | 050-099, 162-199, 277-299 | |
| 274Z | | | KX | 0-0 | 31-41-35 | GDY0009 | S.. | 2 | | D04331P | 28 | | | 150-157, 275-276 | |
| 301B | 24 | PM | C | 2-10 | 27-51-31 | D08034P | 10 | | | D01836A | E14 | | | ALL | |
| 301R | 24 | PM | C | 0-0 | 27-51-31 | D08034P | 11 | | | D01836A | G14 | | | ALL | |
| 301Y | 24 | PM | C | 0-0 | 27-51-31 | D08034P | 12 | | | D01836A | F14 | | | ALL | |
| 302B | 24 | PM | W | 2-9 | 27-58-31 | D08034P | 15 | | | D01836B | C01 | | | ALL | |
| 302R | 24 | PM | W | 0-0 | 27-58-31 | D08034P | 16 | | | D01836B | E01 | | | ALL | |
| 302Y | 24 | PM | W | 0-0 | 27-58-31 | D08034P | 17 | | | D01836B | D01 | | | ALL | |
| 303B | 24 | PM | X | 2-11 | 27-81-11 | D01836B | G10 | | | TB0176F | A015 | 2 | | ALL | |
| 303R | 24 | PM | X | 0-0 | 27-81-11 | D01836B | E10 | | | TB0176F | C014 | 2 | | ALL | |
| 303Y | 24 | PM | X | 0-0 | 27-81-11 | D01836B | F10 | | | TB0176F | C015 | 2 | | ALL | |
| 304B | 24 | PM | AA | 2-9 | 27-81-21 | D01836B | H10 | | | TB0176F | A019 | 2 | | ALL | |
| 304R | 24 | PM | AA | 0-0 | 27-81-21 | D01836B | K10 | | | TB0176F | C019 | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 35

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|----------|---------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 304Y | 24 | PM | AA | 0-0 | 27-81-21 | D01836B | | J10 | | | | TB0176F | A020 | 2 | | ALL |
| 305B | 24 | PM | AC | 3-1 | 27-81-31 | D08024P | | 21 | | | | D01836A | H14 | | | ALL |
| 305R | 24 | PM | AC | 0-0 | 27-81-31 | D08024P | | 22 | | | | D01836A | K14 | | | ALL |
| 305Y | 24 | PM | AC | 0-0 | 27-81-31 | D08024P | | 23 | | | | D01836A | J14 | | | ALL |
| 306B | 24 | PM | AE | 3-7 | 27-81-31 | D05626P | | 17 | | | | D01836A | A15 | | | ALL |
| 306R | 24 | PM | AE | 0-0 | 27-81-31 | D05626P | | 18 | | | | D01836A | C15 | | | ALL |
| 306Y | 24 | PM | AE | 0-0 | 27-81-31 | D05626P | | 19 | | | | D01836A | B15 | | | ALL |
| 309B | 18 | PS | MI | 5-1 | 31-31-25 | D05626P | | 44 | DL | | | D04331P | 12 | DL | | ALL |
| 309R | 18 | PS | MI | 0-0 | 31-31-25 | D05626P | | 41 | DL | | | D04331P | 13 | DL | | ALL |
| 309Y | 18 | PS | MI | 0-0 | 31-31-25 | D05626P | | 42 | DL | | | D04331P | 14 | DL | | ALL |
| 309Z | | | MI | 0-0 | 31-31-25 | D05626P | | 43 | | | | D04331P | 15 | | | ALL |
| 401B | 24 | PN | N | 3-7 | 27-51-41 | D05626P | | 22 | | | | D01836A | J10 | | | ALL |
| 401G | 24 | PN | N | 0-0 | 27-51-41 | D05626P | | 23 | | | | D01836A | B11 | | | ALL |
| 401R | 24 | PN | N | 0-0 | 27-51-41 | D05626P | | 24 | | | | D01836A | K10 | | | ALL |
| 401Y | 24 | PN | N | 0-0 | 27-51-41 | D05626P | | 25 | | | | D01836A | A11 | | | ALL |
| 404B | 24 | PN | Q | 3-7 | 27-51-41 | D05626P | | 11 | | | | D01836A | J13 | | | ALL |
| 404G | 24 | PN | Q | 0-0 | 27-51-41 | D05626P | | 12 | | | | D01836A | B14 | | | ALL |
| 404R | 24 | PN | Q | 0-0 | 27-51-41 | D05626P | | 13 | | | | D01836A | K13 | | | ALL |
| 404Y | 24 | PN | Q | 0-0 | 27-51-41 | D05626P | | 14 | | | | D01836A | A14 | | | ALL |
| 405B | 24 | PN | R | 3-1 | 27-51-41 | D08024P | | 3 | | | | D01836A | E10 | | | ALL |
| 405G | 24 | PN | R | 0-0 | 27-51-41 | D08024P | | 6 | | | | D01836A | H10 | | | ALL |
| 405R | 24 | PN | R | 0-0 | 27-51-41 | D08024P | | 4 | | | | D01836A | F10 | | | ALL |
| 405Y | 24 | PN | R | 0-0 | 27-51-41 | D08024P | | 5 | | | | D01836A | G10 | | | ALL |
| 408B | 24 | PN | U | 3-1 | 27-51-41 | D08024P | | 26 | | | | D01836A | E13 | | | ALL |
| 408G | 24 | PN | U | 0-0 | 27-51-41 | D08024P | | 29 | | | | D01836A | H13 | | | ALL |
| 408R | 24 | PN | U | 0-0 | 27-51-41 | D08024P | | 27 | | | | D01836A | F13 | | | ALL |
| 408Y | 24 | PN | U | 0-0 | 27-51-41 | D08024P | | 28 | | | | D01836A | G13 | | | ALL |
| 409B | 22 | PT | AH | 4-8 | 21-31-21 | D02712A | | D01 | | | | D08034P | 35 | | | ALL |
| 409G | 22 | PT | AH | 0-0 | 21-31-21 | D02712A | | C01 | | | | D08034P | 36 | | | ALL |
| 409R | 22 | PT | AH | 0-0 | 21-31-21 | D02712A | | B01 | | | | D08034P | 37 | | | ALL |
| 409Y | 22 | PT | AH | 0-0 | 21-31-21 | D02712A | | A01 | | | | D08034P | 38 | | | ALL |
| 409Z | | | AH | 0-0 | 21-31-21 | D02712A | | | | FE | | D08034P | 39 | | | ALL |
| 451G | 22 | XU | BQ | 4-2 | 32-46-11 | D02222A | | A08 | 63 | | | D05288P | 2 | | | 050 |
| 451G | 22 | XU | BQ | 4-2 | 32-46-11 | D02222A | | A08 | | | | D05288P | 2 | | | 051-099 |
| 451G | 22 | XU | BQ | 4-2 | 32-46-11 | D02222A | | A08 | 63 | | | D05288P | 2 | 4E | | 150-199, 275-299 |
| 451W | 22 | XU | BQ | 0-0 | 32-46-11 | D02222A | | A07 | 62 | | | D05288P | 1 | | | 050 |
| 451W | 22 | XU | BQ | 0-0 | 32-46-11 | D02222A | | A07 | | | | D05288P | 1 | | | 051-099 |
| 451W | 22 | XU | BQ | 0-0 | 32-46-11 | D02222A | | A07 | 62 | | | D05288P | 1 | 4I | | 150-199, 275-299 |
| 452G | 22 | XU | BR | 4-2 | 32-46-11 | D02222A | | A11 | 63 | | | D05288P | 4 | | | 050 |

WIRE LIST
D280T132

91-21-11
Section W0010
Page 36
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|-----------------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | | | |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 452G | 22 | XU | BR | | 4-2 | 32-46-11 | D02222A | | A11 | | | | D05288P | 4 | | 051-099 |
| 452G | 22 | XU | BR | | 4-2 | 32-46-11 | D02222A | | A11 | 63 | | | D05288P | 4 | 4E | 150-199, 275-299 |
| 452W | 22 | XU | BR | | 0-0 | 32-46-11 | D02222A | | A10 | 62 | | | D05288P | 3 | | 050 |
| 452W | 22 | XU | BR | | 0-0 | 32-46-11 | D02222A | | A10 | | | | D05288P | 3 | | 051-099 |
| 452W | 22 | XU | BR | | 0-0 | 32-46-11 | D02222A | | A10 | 62 | | | D05288P | 3 | 4I | 150-199, 275-299 |
| 453G | 22 | XU | BS | | 5-3 | 32-46-11 | D02222A | | C05 | 63 | | | TB0176F | C088 | 2 | 050, 150-199, 275-299 |
| 453G | 22 | XU | BS | | 5-3 | 32-46-11 | D02222A | | C05 | | | | TB0176F | C088 | 2 | 051-099 |
| 453W | 22 | XU | BS | | 0-0 | 32-46-11 | D02222A | | C04 | 62 | | | TB0176F | A088 | 2 | 050, 150-199, 275-299 |
| 453W | 22 | XU | BS | | 0-0 | 32-46-11 | D02222A | | C04 | | | | TB0176F | A088 | 2 | 051-099 |
| 454G | 22 | XU | BT | | 5-3 | 32-46-11 | D02222A | | C08 | 63 | | | TB0176F | C089 | 2 | 050, 150-199, 275-299 |
| 454G | 22 | XU | BT | | 5-3 | 32-46-11 | D02222A | | C08 | | | | TB0176F | C089 | 2 | 051-099 |
| 454W | 22 | XU | BT | | 0-0 | 32-46-11 | D02222A | | C07 | 62 | | | TB0176F | A089 | 2 | 050, 150-199, 275-299 |
| 454W | 22 | XU | BT | | 0-0 | 32-46-11 | D02222A | | C07 | | | | TB0176F | A089 | 2 | 051-099 |
| 455G | 22 | XU | BU | | 3-3 | 32-46-11 | D02222A | | A02 | 63 | | | D05294P | 2 | | 050 |
| 455G | 22 | XU | BU | | 3-3 | 32-46-11 | D02222A | | A02 | | | | D05294P | 2 | | 051-099 |
| 455G | 22 | XU | BU | | 3-3 | 32-46-11 | D02222A | | A02 | 63 | | | D05294P | 2 | 4F | 150-199, 275-299 |
| 455W | 22 | XU | BU | | 0-0 | 32-46-11 | D02222A | | A01 | 62 | | | D05294P | 1 | | 050 |
| 455W | 22 | XU | BU | | 0-0 | 32-46-11 | D02222A | | A01 | | | | D05294P | 1 | | 051-099 |
| 455W | 22 | XU | BU | | 0-0 | 32-46-11 | D02222A | | A01 | 62 | | | D05294P | 1 | 4J | 150-199, 275-299 |
| 456G | 22 | XU | BV | | 3-3 | 32-46-11 | D02222A | | A05 | 63 | | | D05294P | 4 | | 050 |
| 456G | 22 | XU | BV | | 3-3 | 32-46-11 | D02222A | | A05 | | | | D05294P | 4 | | 051-099 |
| 456G | 22 | XU | BV | | 3-3 | 32-46-11 | D02222A | | A05 | 63 | | | D05294P | 4 | 4F | 150-199, 275-299 |
| 456W | 22 | XU | BV | | 0-0 | 32-46-11 | D02222A | | A04 | 62 | | | D05294P | 3 | | 050 |
| 456W | 22 | XU | BV | | 0-0 | 32-46-11 | D02222A | | A04 | | | | D05294P | 3 | | 051-099 |
| 456W | 22 | XU | BV | | 0-0 | 32-46-11 | D02222A | | A04 | 62 | | | D05294P | 3 | 4J | 150-199, 275-299 |
| 457G | 22 | XU | BW | | 3-11 | 32-46-11 | D02222A | | A14 | 63 | | | TB0176F | C131 | 2 | 050 |
| 457G | 22 | XU | BW | | 3-11 | 32-46-11 | D02222A | | A14 | | | | TB0176F | C131 | 2 | 051-099 |
| 457G | 22 | XU | BW | | 3-10 | 32-46-11 | D02222A | | A14 | 63 | | | TB0176F | C131 | 2 | 150-199, 275-299 |
| 457W | 22 | XU | BW | | 0-0 | 32-46-11 | D02222A | | A13 | 62 | | | TB0176F | A131 | 2 | 050, 150-199, 275-299 |
| 457W | 22 | XU | BW | | 0-0 | 32-46-11 | D02222A | | A13 | | | | TB0176F | A131 | 2 | 051-099 |
| 458G | 22 | XU | BX | | 4-10 | 32-46-11 | D02222A | | C02 | 63 | | | TB0176F | C072 | 2 | 050, 150-199, 275-299 |
| 458G | 22 | XU | BX | | 4-10 | 32-46-11 | D02222A | | C02 | | | | TB0176F | C072 | 2 | 051-099 |
| 458W | 22 | XU | BX | | 0-0 | 32-46-11 | D02222A | | C01 | 62 | | | TB0176F | A072 | 2 | 050, 150-199, 275-299 |
| 458W | 22 | XU | BX | | 0-0 | 32-46-11 | D02222A | | C01 | | | | TB0176F | A072 | 2 | 051-099 |
| 501 | 24 | PV | BD | | 4-1 | 29-11-31 | D04110P | | | 34 | | | TB0176F | A108 | 2 | ALL |
| 501Z | | | BD | | 0-0 | 29-11-31 | D04110P | | DED | | | | TB0176F | DED | | ALL |
| 502 | 24 | PV | BH | | 3-9 | 24-51-13 | D04110P | | | 3 | | | TB0176F | A109 | 2 | 050-099 |
| 502 | 24 | PV | BH | | 3-11 | 24-51-13 | D04110P | | | 3 | | | TB0176F | A109 | 2 | 150-199, 275-299 |
| 502Z | | | BH | | 0-0 | 24-51-13 | D04110P | | DED | | | | TB0176F | DED | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 37

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 505 | 24 | | PK | | 2-4 | 21-31-21 | D02712A | | D10 | | D02712A | | D11 | | ALL |
| 506 | 24 | | PK | | 2-4 | 21-31-21 | D02712A | | B09 | | D02712A | | B10 | | ALL |
| 507 | 24 | | PK | | 3-1 | 77-31-11 | D05626P | | 36 | | D02708C | | 2 | | ALL |
| 510 | 22 | | PA | | 4-2 | 29-33-11 | D05734P | | 14 | | TB0176G | | 154 | 2 | ALL |
| 514 | 22 | | PA | | 4-2 | 29-33-11 | D05734P | | 11 | | TB0176G | | 155 | 2 | ALL |
| 516 | 22 | | PA | | 6-0 | 32-46-11 | TB0176G | | 96 | 2 | D04862P | | 2 | | ALL |
| 518 | 22 | | PA | | 3-9 | 32-46-11 | D02222B | | D14 | | GDX0008 | | D.. | 2 | 050-099 |
| 518 | 22 | | PA | | 5-0 | 32-46-11 | D02222B | | D14 | | GDX0008 | | D.. | 2 | 150-199, 275-299 |
| 519 | 22 | | PA | | 3-9 | 32-46-11 | D02222B | | C15 | | GDX0008 | | S.. | 2 | 050-099 |
| 519 | 22 | | PA | | 5-0 | 32-46-11 | D02222B | | C15 | | GDX0008 | | S.. | 2 | 150-199, 275-299 |
| 520 | 24 | | PK | | 3-3 | 32-46-11 | D02222B | | D12 | | D05202P | | 18 | | 050-099 |
| 520 | 24 | | PK | | 4-0 | 32-46-11 | D02222B | | D12 | | D05202P | | 18 | | 150-199, 275-299 |
| 521 | 24 | | PK | | 3-3 | 32-46-11 | D02222B | | C10 | | D05202P | | 11 | | 050-099 |
| 521 | 24 | | PK | | 4-0 | 32-46-11 | D02222B | | C10 | | D05202P | | 11 | | 150-199, 275-299 |
| 522 | 24 | | PK | | 3-3 | 32-46-11 | D02222B | | C11 | | D05202P | | 12 | | 050-099 |
| 522 | 24 | | PK | | 4-0 | 32-46-11 | D02222B | | C11 | | D05202P | | 12 | | 150-199, 275-299 |
| 523 | 24 | | PK | | 3-3 | 32-46-11 | D02222B | | C12 | | D05202P | | 13 | | 050-099 |
| 523 | 24 | | PK | | 4-0 | 32-46-11 | D02222B | | C12 | | D05202P | | 13 | | 150-199, 275-299 |
| 524 | 24 | | PK | | 3-3 | 32-46-11 | D02222B | | C13 | | D05202P | | 14 | | 050-099 |
| 524 | 24 | | PK | | 4-0 | 32-46-11 | D02222B | | C13 | | D05202P | | 14 | | 150-199, 275-299 |
| 525 | 24 | | PK | | 3-3 | 32-46-11 | D02222B | | D09 | | D05202P | | 15 | | 050-099 |
| 525 | 24 | | PK | | 4-0 | 32-46-11 | D02222B | | D09 | | D05202P | | 15 | | 150-199, 275-299 |
| 526 | 24 | | PK | | 3-3 | 32-46-11 | D02222B | | D10 | | D05202P | | 16 | | 050-099 |
| 526 | 24 | | PK | | 4-0 | 32-46-11 | D02222B | | D10 | | D05202P | | 16 | | 150-199, 275-299 |
| 527 | 24 | | PK | | 3-3 | 32-46-11 | D02222B | | D11 | | D05202P | | 17 | | 050-099 |
| 527 | 24 | | PK | | 4-0 | 32-46-11 | D02222B | | D11 | | D05202P | | 17 | | 150-199, 275-299 |
| 537 | 24 | | PK | | 3-2 | 32-46-11 | D02222B | | D05 | | D04862P | | 1 | | 050-099 |
| 537 | 24 | | PK | | 4-0 | 32-46-11 | D02222B | | D05 | | D04862P | | 1 | | 150-199, 275-299 |
| 538 | 20 | | UA | | 3-7 | 77-31-11 | D02708A | | REF | | GDX0002 | | S.. | 2 | 050-099 |
| 538 | 20 | | UA | | 3-7 | 77-31-11 | D02708A | | | FX | GDX0002 | | S.. | 2 | 150-199, 275-299 |
| 543 | 24 | | PK | | 3-6 | 27-51-51 | D01836A | | F03 | | TB0176G | | 148 | 2 | ALL |
| 544 | 24 | | PK | | 3-5 | 27-51-51 | D01836B | | G04 | | TB0176G | | 148 | 2 | 050-099 |
| 544 | 24 | | PK | | 3-7 | 27-51-51 | D01836B | | G04 | | TB0176G | | 148 | 2 | 150-199, 275-299 |
| 545 | 22 | | PA | | 3-2 | 27-51-61 | D01836A | | C06 | | GDX0008 | | D.. | 2 | ALL |
| 546 | 22 | | PA | | 3-1 | 27-51-61 | D01836B | | K03 | | GDX0008 | | D.. | 2 | ALL |
| 547 | 22 | | PA | | 3-1 | 27-51-61 | D01836B | | J03 | | GDX0008 | | D.. | 2 | ALL |
| 549 | 24 | | PK | | 2-8 | 27-51-11 | D01836A | | J01 | | TB0176G | | 22 | 2 | ALL |
| 550 | 24 | | PK | | 2-7 | 27-51-11 | D01836B | | A05 | | TB0176G | | 22 | 2 | ALL |
| 551 | 24 | | PK | | 4-7 | 27-51-11 | D01836A | | A05 | | TB0176F | | A090 | 2 | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 38

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0014 | 286T0014 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 552 | 24 | | PK | 4-7 | 27-51-11 | D01836A | B05 | | | | TB0176F | C090 | 2 | | ALL |
| 553 | 24 | | PK | 4-7 | 27-51-11 | D01836A | C05 | | | | TB0176F | A091 | 2 | | 050-099 |
| 553 | 24 | | PK | 5-1 | 27-51-11 | D01836A | C05 | | | | TB0176F | A091 | 2 | | 150-199, 275-299 |
| 554 | 24 | | PK | 5-1 | 27-51-11 | D01836B | F05 | | | | TB0176F | C092 | 2 | | ALL |
| 555 | 24 | | PK | 5-1 | 27-51-11 | D01836B | G05 | | | | TB0176F | A093 | 2 | | ALL |
| 556 | 24 | | PK | 5-1 | 27-51-11 | D01836B | H05 | | | | TB0176F | C093 | 2 | | ALL |
| 557 | 24 | | PK | 5-1 | 27-51-11 | D01836B | J05 | | | | TB0176F | A094 | 2 | | ALL |
| 558 | 24 | | PK | 5-1 | 27-51-11 | D01836B | K05 | | | | TB0176F | C094 | 2 | | ALL |
| 559 | 24 | | PK | 2-8 | 27-51-51 | D01836B | E06 | | | | D05202P | 4 | | | ALL |
| 560 | 24 | | PK | 4-6 | 27-58-31 | D05202P | 5 | | | | TB0176G | 68 | 2 | | ALL |
| 561 | 24 | | PK | 5-3 | 27-81-11 | D01836A | C01 | | | | TB0176G | 95 | 2 | | ALL |
| 562 | 24 | | PK | 5-1 | 27-81-11 | D01836B | B05 | | | | TB0176G | 95 | 2 | | ALL |
| 564 | 24 | | PK | 4-6 | 27-51-11 | D01836B | D05 | | | | TB0176F | C091 | 2 | | 050-099 |
| 564 | 24 | | PK | 5-1 | 27-51-11 | D01836B | D05 | | | | TB0176F | C091 | 2 | | 150-199, 275-299 |
| 565 | 24 | | PK | 5-1 | 27-51-11 | D01836B | E05 | | | | TB0176F | A092 | 2 | | ALL |
| 566 | 24 | | PK | 3-3 | 28-41-11 | D05202P | 2 | | | | TB0176F | A009 | 2 | | ALL |
| 567 | 24 | | PK | 3-4 | 24-51-71 | D04960P | 1 | | | | TB0176G | 61 | 2 | | ALL |
| 568 | 24 | | PK | 2-11 | 24-51-71 | D04960P | 2 | | | | TB0176F | A039 | 2 | | ALL |
| 569 | 24 | | PK | 4-0 | 24-11-11 | D04110P | 9 | | | | TB0176F | A016 | 2 | | ALL |
| 574 | 24 | | PK | 3-0 | 27-88-11 | TB0176G | 136 | | 2 | | TB0176D | C132 | 2 | | ALL |
| 575 | 24 | | PK | 3-0 | 27-88-11 | TB0176G | 136 | | 2 | | TB0176D | C133 | 2 | | ALL |
| 576 | 24 | | PK | 2-11 | 27-88-11 | D05626P | 32 | | | | TB0176D | A133 | 2 | | ALL |
| 577 | 24 | | PK | 3-9 | 29-11-22 | D08024P | 39 | | | | TB0176D | A132 | 2 | | ALL |
| 578 | 24 | | PK | 4-0 | 29-11-22 | D08024P | 38 | | | | D04110P | 37 | | | ALL |
| 582 | 22 | | PA | 6-4 | 32-46-11 | D02222B | C07 | | | | TB0176G | 96 | 2 | | ALL |
| 583 | 24 | | PK | 6-0 | 32-46-11 | D05202P | 10 | | | | TB0176G | 96 | 2 | | ALL |
| 589 | 24 | | PK | 2-7 | 27-51-11 | TB0176F | C026 | | 2 | | D01836B | A14 | | | ALL |
| 590 | 24 | | PK | 2-10 | 27-51-31 | D08034P | 4 | | | | D01836A | D01 | | | ALL |
| 591 | 24 | | PK | 2-9 | 27-58-31 | D08034P | 18 | | | | D01836B | C02 | | | ALL |
| 594 | 22 | | PA | 2-5 | 27-51-61 | D01836A | E06 | | | | GDX0001 | D.. | 2 | | 150-199, 275-299 |
| 595 | 22 | | PA | 2-4 | 27-51-61 | D01836B | D02 | | | | GDX0001 | D.. | 2 | | 150-199, 275-299 |
| 596 | 22 | | PA | 2-4 | 27-51-61 | D01836B | F14 | | | | GDX0001 | D.. | 2 | | 150-199, 275-299 |
| 599 | 22 | | PA | 3-0 | 77-31-11 | D02708A | D15 | | | | TB0176 | G044 | BJ | | 150-154 |
| 602 | 24 | | PK | 3-11 | 77-35-11 | D05626P | 8 | | | | TB0176F | A177 | 2 | | ALL |
| 603 | 22 | | PA | 2-1 | 27-51-61 | D01836A | E06 | | | | GDX0003 | D.. | 2 | | 050-099 |
| 604 | 22 | | PA | 2-1 | 27-51-61 | D01836A | F06 | | | | GDX0003 | D.. | 2 | | 050-099 |
| 605 | 22 | | PA | 2-1 | 27-51-61 | D01836A | G06 | | | | GDX0003 | D.. | 2 | | 050-099 |
| 606 | 22 | | PA | 3-11 | 27-51-61 | D01836B | D02 | | | | GDX0012 | D.. | 2 | | 050-099 |
| 607 | 22 | | PA | 3-11 | 27-51-61 | D01836B | E02 | | | | GDX0012 | D.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 39

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|--|-------|------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0014 | 286T0014 | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | |
| 608 | 22 | PA | | 2-0 | 27-51-61 | D01836B | | E14 | | | GDX0003 | D.. | 2 | | 050-099 |
| 609 | 22 | PA | | 2-0 | 27-51-61 | D01836B | | F14 | | | GDX0003 | D.. | 2 | | 050-099 |
| 611 | 22 | PA | | 5-4 | 31-31-22 | D04331P | | 21 | | | TB0176F | A059 | 2 | | ALL |
| 612 | 24 | PK | | 4-1 | 31-31-26 | TB0176F | | A027 | 2 | | D04331P | 22 | | | ALL |
| 613 | 24 | PK | | 4-0 | 31-31-26 | D04110P | | 38 | | | TB0176F | C020 | 2 | | 050-099 |
| 613 | 24 | PK | | 3-10 | 31-31-26 | D04110P | | 38 | | | TB0176F | C020 | 2 | | 150-199, 275-299 |
| 614 | 24 | PK | | 7-0 | 31-31-26 | D04110P | | 39 | | | D04331P | 17 | | | 050-099 |
| 614 | 24 | PK | | 5-0 | 31-31-26 | D04110P | | 39 | | | D04331P | 17 | | | 150-199, 275-299 |
| 616 | 22 | PA | | 3-0 | 77-31-11 | D02708A | | B11 | | | TB0176 | G044 | BJ | | 150-154 |
| 617 | 22 | PA | | 3-0 | 77-31-11 | D02708A | | B12 | | | TB0176 | G044 | BJ | | 150-154 |
| 621 | 24 | PK | | 3-1 | 27-81-31 | D01836A | | D02 | | | TB0176F | C016 | 2 | | ALL |
| 622 | 24 | PK | | 3-1 | 27-81-31 | D08024P | | 40 | | | D01836A | F08 | | | ALL |
| 623 | 24 | PK | | 3-1 | 27-81-31 | D08024P | | 41 | | | D01836A | G08 | | | ALL |
| 630 | 24 | PK | | 2-10 | 27-51-61 | M02188 | | B | D | | D08034P | 6 | | | 050-099 |
| 630 | 24 | PK | | 4-0 | 27-51-61 | M02188 | | B | D | | D08034P | 6 | | | 150-199, 275-299 |
| 632 | 22 | PA | | 3-0 | 29-33-11 | D02704A | | A12 | | | GDZ0001 | S.. | E | *2 | ALL |
| 633 | 22 | PA | | 3-0 | 29-33-11 | D02704A | | A03 | | | GDZ0001 | S.. | E | *3 | ALL |
| FRH | | | | 0-0 | 29-33-11 | D02704A | | REF | | FP | D02704A | C03 | | | 050-099 |
| FRH | | | | 2-2 | 29-33-11 | D02704A | | REF | | FP | D02704A | C03 | | | 150-199, 275-299 |
| FRI | | | | 2-2 | 29-33-11 | D02704A | | REF | | FO | GDZ0001 | S.. | E | *2 | ALL |
| FRK | | | | 0-0 | 29-33-11 | D02704A | | REF | | FP | D02704A | B03 | | | 050-099 |
| FRK | | | | 2-2 | 29-33-11 | D02704A | | REF | | FP | D02704A | B03 | | | 150-199, 275-299 |
| FRL | | | | 0-0 | 29-33-11 | D02704A | | REF | | FO | D02704A | B12 | | | 050-099 |
| FRL | | | | 2-2 | 29-33-11 | D02704A | | REF | | FO | D02704A | B12 | | | 150-199, 275-299 |
| FRO | | | | 0-0 | 29-33-11 | D02704A | | REF | | FO | D02704A | C12 | | | 050-099 |
| FRO | | | | 2-2 | 29-33-11 | D02704A | | REF | | FO | D02704A | C12 | | | 150-199, 275-299 |
| FRP | | | | 2-2 | 29-33-11 | D02704A | | REF | | FP | GDZ0001 | S.. | E | *3 | ALL |
| FRQ | | | | 0-0 | 73-21-14 | D08034P | | | | FQ | D08034P | 48 | | | ALL |
| FRR | | | | 0-0 | 29-33-11 | D05734P | | REF | | FW | D05734P | 7 | | | ALL |
| FRS | | | | 0-0 | 29-33-11 | D05734P | | REF | | FW | D05734P | 18 | | | ALL |
| FRT | | | | 0-0 | 29-33-11 | D05364P | | REF | | FT | D05364P | 2 | | | ALL |
| FRU | | | | 0-0 | 29-33-11 | D05364P | | REF | | FT | D05364P | 10 | | | ALL |
| FRV | | | | 0-0 | 29-33-11 | D05364P | | REF | | FT | D05364P | 12 | | | ALL |
| FRW | | | | 0-0 | 29-33-11 | D05734P | | REF | | FW | D05734P | 6 | | | ALL |
| W0016 | 286T0016 | SHELF E2-4 INTEGRATION BUNDLE | | | | | | | | | | | | | |
| 001 | 22 | PA | | 5-1 | 27-51-11 | D05622P | | 1 | | | TB0176F | C002 | 2 | | ALL |
| 002 | 22 | PA | | 5-1 | 27-51-11 | D05622P | | 2 | | | TB0176F | A002 | 2 | | ALL |
| 003 | 22 | PA | | 4-10 | 27-51-11 | D05622P | | 3 | | | TB0176F | A105 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0010
 Page 40
 May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0016 | 286T0016 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 004 | 24 | | PK | 4-4 | 27-51-61 | M02189 | B | D | | D05622P | 15 | | | 050-099 | |
| 004 | 24 | | PK | 5-1 | 27-51-61 | M02189 | B | D | | D05622P | 15 | | | 150-199, 275-299 | |
| 005 | 24 | | PK | 5-1 | 27-51-61 | D05622P | 16 | | | TB0176F | C003 | 2 | | ALL | |
| 006 | 24 | | PK | 5-1 | 27-51-11 | D05622P | 17 | | | TB0176F | A004 | 2 | | ALL | |
| 007 | 24 | | PK | 5-1 | 27-51-11 | D05622P | 18 | | | TB0176F | C004 | 2 | | ALL | |
| 008 | 24 | | PK | 4-11 | 27-51-11 | D05622P | 19 | | | TB0176F | A005 | 2 | | ALL | |
| 009 | 24 | | PK | 4-11 | 27-51-11 | D05622P | 20 | | | TB0176F | C005 | 2 | | ALL | |
| 010 | 24 | | PK | 4-11 | 27-51-11 | D05622P | 21 | | | TB0176F | A006 | 2 | | ALL | |
| 011 | 24 | | PK | 4-11 | 27-51-11 | D05622P | 22 | | | TB0176F | C006 | 2 | | ALL | |
| 012 | 24 | | PK | 4-11 | 27-51-11 | D05622P | 23 | | | TB0176F | A007 | 2 | | ALL | |
| 013 | 24 | | PK | 4-11 | 27-51-11 | D05622P | 24 | | | TB0176F | C007 | 2 | | ALL | |
| 014 | 22 | | PA | 4-10 | 27-81-11 | D05622P | 4 | | | TB0176F | A013 | 2 | | ALL | |
| 015 | 22 | | PA | 4-10 | 27-81-11 | D05622P | 5 | | | TB0176F | C009 | 2 | | ALL | |
| 016 | 22 | | PA | 4-10 | 27-81-11 | D05622P | 6 | | | TB0176F | A106 | 2 | | ALL | |
| 017 | 22 | | PA | 4-9 | 27-81-21 | D05622P | 7 | | | TB0176F | A017 | 2 | | ALL | |
| 018 | 22 | | PA | 4-9 | 27-81-21 | D05622P | 8 | | | TB0176F | C017 | 2 | | ALL | |
| 019 | 22 | | PA | 3-1 | 27-81-21 | D05622P | 9 | | | TB0176F | A097 | 2 | | ALL | |
| 020 | 22 | | PA | 3-3 | 24-11-21 | D00256B | A03 | | | TB0176F | A084 | 2 | | ALL | |
| 021 | 22 | | PA | 4-6 | 24-11-21 | D00256B | D15 | | | GD0001 | D.. | 2 | | ALL | |
| 022 | 22 | | PA | 4-6 | 24-11-21 | D00256B | A08 | | | GD0001 | S.. | 2 | | ALL | |
| 023 | 24 | | PK | 5-2 | 24-11-11 | D00256A | A02 | | | TB0176F | A016 | 2 | | ALL | |
| 025 | 24 | | PK | 4-5 | 24-11-21 | D00256B | D08 | | | TB0176R | C139 | 2 | | ALL | |
| 026 | 24 | | PK | 2-11 | 24-11-21 | D00256A | C04 | | | D04034P | 17 | | | ALL | |
| 027 | 22 | | PQ | 4-11 | 24-11-21 | D00256A | D02 | | | TB0176G | 23 | 2 | | ALL | |
| 027Z | | | AE | 0-0 | 24-11-21 | D00256A | DED | | | TB0176G | DED | | | ALL | |
| 028 | 24 | | PK | 3-7 | 29-11-12 | D05204P | 14 | | | D04078P | 20 | | | ALL | |
| 029 | 18 | | PQ | 5-3 | 24-11-21 | D04036P | 4 | | | TB0176G | 23 | 2 | | ALL | |
| 029Z | | | AF | 0-0 | 24-11-21 | D04036P | DED | | | TB0176G | DED | | | ALL | |
| 030 | 24 | | PK | 2-11 | 24-11-21 | D00256A | C06 | | | D04034P | 16 | | | ALL | |
| 031 | 24 | | PK | 3-11 | 24-11-21 | TB0176G | 41 | 2 | | D04034P | 38 | | | 050-099 | |
| 031 | 24 | | PK | 3-9 | 24-11-21 | TB0176G | 41 | 2 | | D04034P | 38 | | | 150-199, 275-299 | |
| 033 | 24 | | PK | 2-2 | 31-51-41 | D05715P | 23 | | | TB0176G | 68 | 2 | | 050-099 | |
| 033 | 24 | | PK | 2-7 | 31-51-41 | D05715P | 23 | | | TB0176G | 68 | 2 | | 150-199, 275-299 | |
| 034 | 24 | | PK | 2-7 | 31-51-21 | D05715P | 1 | | | TB0176F | A070 | 2 | | 150-154, 275 | |
| 035 | 24 | | PK | 5-1 | 24-11-21 | TB0176R | A139 | 2 | | D04034P | 23 | | | ALL | |
| 036 | 24 | | PK | 5-3 | 24-27-21 | TB0176G | 11 | 2 | | D04078P | 13 | | | ALL | |
| 037 | 24 | | PK | 2-11 | 24-22-21 | D00256A | D04 | | | D04034P | 19 | | | ALL | |
| 038 | 22 | | PA | 3-11 | 24-51-52 | D05204P | 5 | | | TB0176G | 62 | 2 | | 050-099 | |
| 038 | 22 | | PA | 3-10 | 24-51-52 | D05204P | 5 | | | TB0176G | 62 | 2 | | 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 41

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0016 | 286T0016 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | |
| 039 | 24 | | PK | | 2-11 | 24-22-21 | D04034P | | 32 | | | | D00256A | B05 | | | ALL |
| 040 | 20 | | PA | | 4-3 | 24-22-21 | D04034P | | 29 | | | | TB0176G | 31 | 2 | | ALL |
| 041 | 20 | | PA | | 4-3 | 24-22-21 | D04034P | | 35 | | | | TB0176G | 31 | 2 | | ALL |
| 042 | 24 | | PK | | 2-11 | 24-22-21 | D04034P | | 31 | | | | D00256A | C02 | | | ALL |
| 043 | 24 | | PK | | 2-11 | 24-22-21 | D04034P | | 24 | | | | D00256A | A05 | | | ALL |
| 044 | 24 | | PK | | 2-11 | 24-22-21 | D04034P | | 37 | | | | D00256A | D06 | | | ALL |
| 045 | 24 | | PK | | 2-11 | 24-22-22 | D04034P | | 36 | | | | D00256A | D05 | | | ALL |
| 046 | 24 | | PK | | 2-8 | 24-22-21 | D05204P | | 13 | | | | D00256A | A01 | | | ALL |
| 047 | 22 | | PA | | 4-4 | 24-22-21 | D00256A | | A07 | | | | GD00002 | D.. | 2 | | ALL |
| 050 | 24 | | PK | | 4-3 | 24-22-22 | D04034P | | 44 | | | | TB0176F | C032 | 2 | | ALL |
| 051 | 24 | | PK | | 4-2 | 24-22-22 | D04034P | | 45 | | | | TB0176F | A033 | 2 | | ALL |
| 052 | 24 | | PK | | 2-11 | 24-22-22 | D04034P | | 39 | | | | D00256A | D08 | | | ALL |
| 053 | 20 | | PA | | 4-2 | 24-22-22 | D04034P | | 40 | | | | TB0176G | 35 | 2 | | ALL |
| 054 | 20 | | PA | | 4-2 | 24-22-22 | D04034P | | 41 | | | | TB0176G | 35 | 2 | | ALL |
| 055 | 22 | | PA | | 4-2 | 25-31-11 | D04034P | | 4 | | | | TB0176G | 37 | 2 | | ALL |
| 056 | 22 | | PA | | 4-2 | 25-31-11 | D04034P | | 25 | | | | TB0176F | A038 | 2 | | ALL |
| 057 | 24 | | PK | | 5-3 | 24-27-21 | D04078P | | 14 | | | | TB0176G | 11 | 2 | | ALL |
| 058 | 24 | | PK | | 5-2 | 24-27-21 | D00256A | | D07 | | | | TB0176G | 11 | 2 | | ALL |
| 060 | 24 | | PK | | 3-9 | 24-28-21 | D00256A | | B02 | | | | TB0176G | 164 | 2 | | ALL |
| 061 | 24 | | PK | | 3-9 | 24-28-21 | D00256A | | A10 | | | | TB0176G | 164 | 2 | | ALL |
| 077 | 24 | | PK | | 3-7 | 29-11-12 | D04078P | | 23 | | | | D05204P | 15 | | | ALL |
| 084 | 24 | | PK | | 3-7 | 29-11-12 | D04078P | | 22 | | | | D05204P | 12 | | | ALL |
| 085 | 24 | | PK | | 4-9 | 27-51-11 | TB0176F | | C026 | 2 | | | D06140P | 11 | | | ALL |
| 086 | 24 | | PK | | 3-10 | 33-24-11 | D05204P | | 7 | | | | TB0176F | A075 | 2 | | ALL |
| 087 | 24 | | PV | AK | 4-7 | 29-33-11 | D04916P | | 9 | | | | TB0176G | 117 | 2 | | ALL |
| 087Z | | | | AK | 0-0 | 29-33-11 | D04916P | | DED | | | | TB0176G | DED | | | ALL |
| 088 | 24 | | PV | BZ | 3-1 | 29-33-11 | D04916P | | 10 | | | | TB0176F | C156 | 2 | | ALL |
| 088Z | | | | BZ | 0-0 | 29-33-11 | D04916P | | DED | | | | TB0176F | DED | | | ALL |
| 090 | 22 | | PQ | AX | 3-1 | 29-33-11 | D04916P | | 12 | | | | TB0176F | A156 | 2 | | ALL |
| 090Z | | | | AX | 0-0 | 29-33-11 | D04916P | | DED | | | | TB0176F | DED | | | ALL |
| 091 | 24 | | PV | Z | 4-5 | 29-33-11 | D04916P | | 15 | | | | D02704B | B05 | | | ALL |
| 091Z | | | | Z | 0-0 | 29-33-11 | D04916P | | | | FD | | D02704B | | | FN | ALL |
| 092 | 24 | | PK | | 2-7 | 29-33-11 | D04916P | | 2 | | | | TB0176F | A082 | 2 | | ALL |
| 093 | 24 | | PK | | 2-7 | 29-33-11 | D04916P | | 3 | | | | TB0176F | C082 | 2 | | ALL |
| 094 | 24 | | PK | | 2-7 | 29-33-11 | D04916P | | 6 | | | | TB0176F | A083 | 2 | | ALL |
| 098 | 24 | | PK | | 2-11 | 24-11-21 | D00256A | | C03 | | | | D04034P | 22 | | | 150-199 |
| 100 | 22 | | PA | | 0-6 | 24-21-21 | D00256B | | A15 | | | | SM00001 | | W | | ALL |
| 101 | 22 | | PA | | 0-6 | 24-21-21 | D00256B | | B15 | | | | SM00002 | | W | | ALL |
| 102 | 22 | | PA | | 0-6 | 24-21-21 | D00256B | | C15 | | | | SM00003 | | W | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0010
 Page 42
 May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|---------|-------|------|------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0016 | 286T0016 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 103 | 22 | | PA | 2-11 | 24-22-21 | D04034P | | 30 | | D00256B | D02 | | | ALL | |
| 104 | 24 | | PK | 4-3 | 24-22-21 | D00256A | | C05 | | TB0176G | 31 | 2 | | ALL | |
| 105 | 22 | | PA | 2-11 | 24-22-21 | D04034P | | 34 | | D00256A | B01 | | | ALL | |
| 106 | 22 | | PA | 2-11 | 24-22-21 | D04034P | | 33 | | D00256A | C01 | | | ALL | |
| 107 | 18 | | PA | 3-0 | 24-22-21 | D04036P | | 7 | | SM00004 | | W | | ALL | |
| 108 | 22 | | PA | 0-6 | 24-22-21 | D00256A | | C15 | | SM00004 | | W | | ALL | |
| 109 | 24 | | PK | 4-2 | 24-22-22 | D00256A | | A08 | | TB0176G | 35 | 2 | | ALL | |
| 110 | 22 | | PA | 2-11 | 24-22-22 | D00256A | | C07 | | D04034P | 42 | | | ALL | |
| 111 | 22 | | PA | 2-11 | 24-22-22 | D00256A | | C08 | | D04034P | 43 | | | ALL | |
| 112 | 18 | | PA | 3-0 | 24-22-22 | D04036P | | 8 | | SM00005 | | W | | ALL | |
| 113 | 22 | | PA | 0-6 | 24-22-22 | D00256A | | D15 | | SM00005 | | W | | ALL | |
| 114 | 24 | | PK | 4-1 | 31-51-21 | D05715P | | 4 | | TB0176F | C021 | 2 | | 150-154, 275 | |
| 115 | 24 | | PK | 2-7 | 27-32-11 | D05715P | | 8 | | TB0176F | A069 | 2 | | ALL | |
| 116 | 24 | | PK | 2-7 | 27-32-11 | D05715P | | 9 | | TB0176F | C069 | 2 | | ALL | |
| 117 | 24 | | PK | 2-11 | 27-32-11 | D05715P | | 10 | | TB0176F | C050 | 2 | | ALL | |
| 118 | 24 | | PK | 4-5 | 27-32-11 | D05715P | | 11 | | TB0176F | C110 | 2 | | ALL | |
| 119 | 24 | | PK | 4-4 | 27-32-21 | D05715P | | 12 | | TB0176F | A113 | 2 | | ALL | |
| 120 | 24 | | PK | 4-4 | 27-32-21 | D05715P | | 13 | | TB0176F | C113 | 2 | | ALL | |
| 121 | 24 | | PK | 4-4 | 27-32-21 | D05715P | | 14 | | TB0176F | A114 | 2 | | ALL | |
| 122 | 24 | | PK | 4-4 | 27-32-21 | D05715P | | 15 | | TB0176F | C114 | 2 | | ALL | |
| 124 | 24 | | PK | 4-9 | 21-31-21 | D05622P | | 52 | | TB0176D | C116 | 2 | | ALL | |
| 125 | 24 | | PV | S | 3-5 | 24-22-11 | D00256A | A06 | | TB0176F | A079 | 2 | | 050-099 | |
| 125 | 24 | | PV | S | 3-0 | 24-22-11 | D00256A | A06 | | TB0176F | A079 | 2 | | 150-199, 275-299 | |
| 125Z | | | | S | 0-0 | 24-22-11 | D00256A | DED | | TB0176F | DED | | | ALL | |
| 126 | 24 | | PK | 6-4 | 24-51-31 | D04034P | | 46 | | TB0176F | C102 | 2 | | ALL | |
| 127 | 20 | | PA | 6-4 | 24-22-22 | D04034P | | 47 | | TB0176F | A102 | 2 | | ALL | |
| 128 | 24 | | PK | 6-4 | 24-51-31 | D04034P | | 48 | | TB0176F | C101 | 2 | | ALL | |
| 129 | 20 | | PA | 6-4 | 24-22-22 | D04034P | | 49 | | TB0176F | A103 | 2 | | ALL | |
| 130 | 24 | | PV | BA | 5-2 | 29-11-31 | D04034P | 50 | | TB0176F | A107 | 2 | | ALL | |
| 130Z | | | | BA | 0-0 | 29-11-31 | D04034P | DED | | TB0176F | DED | | | ALL | |
| 131 | 24 | | PV | BE | 6-2 | 29-11-31 | D04034P | 51 | | TB0176F | C107 | 2 | | ALL | |
| 131Z | | | | BE | 0-0 | 29-11-31 | D04034P | DED | | TB0176F | DED | | | ALL | |
| 132 | 24 | | PV | BF | 3-6 | 29-11-31 | D04034P | 52 | | D05204P | 8 | | | ALL | |
| 132Z | | | | BF | 0-0 | 29-11-31 | D04034P | DED | | D05204P | DED | | | ALL | |
| 133 | 24 | | PV | T | 6-4 | 29-11-31 | D05204P | 6 | | TB0176F | A108 | 2 | | ALL | |
| 133Z | | | | T | 0-0 | 29-11-31 | D05204P | DED | | TB0176F | DED | | | ALL | |
| 134 | 24 | | PV | BC | 6-2 | 24-51-23 | D04036P | 13 | | TB0176F | A121 | 2 | | ALL | |
| 134Z | | | | BC | 0-0 | 24-51-23 | D04036P | DED | | TB0176F | DED | | | ALL | |
| 138 | 24 | | PK | 5-2 | 24-51-51 | D04036P | | 12 | | TB0176G | 144 | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 43

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0016 | 286T0016 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 139 | 22 | PA | | | 4-0 | 24-51-51 | D04078P | | 15 | | | TB0176G | 81 | 2 | | ALL |
| 140 | 22 | PA | | | 5-11 | 24-51-51 | D04078P | | 16 | | | TB0176F | A123 | 2 | | ALL |
| 141 | 24 | PK | | | 5-10 | 24-51-31 | D04034P | | 28 | | | TB0176F | C123 | 2 | | ALL |
| 146 | 24 | PK | | | 4-10 | 24-51-51 | D04078P | | 17 | | | TB0176G | 144 | 2 | | ALL |
| 147 | 24 | PK | | | 2-11 | 27-51-11 | D06140P | | 8 | | | TB0176F | A090 | 2 | | ALL |
| 148 | 24 | PK | | | 2-11 | 27-51-11 | D06140P | | 9 | | | TB0176F | C090 | 2 | | ALL |
| 149 | 24 | PK | | | 2-11 | 27-51-11 | D06140P | | 10 | | | TB0176F | A091 | 2 | | ALL |
| 150 | 24 | PK | | | 2-11 | 27-51-11 | D06140P | | 1 | | | TB0176F | C091 | 2 | | ALL |
| 151 | 24 | PK | | | 3-2 | 27-51-11 | D06140P | | 2 | | | TB0176F | A092 | 2 | | ALL |
| 152 | 24 | PK | | | 3-2 | 27-51-11 | D06140P | | 3 | | | TB0176F | C092 | 2 | | ALL |
| 153 | 24 | PK | | | 3-2 | 27-51-11 | D06140P | | 4 | | | TB0176F | A093 | 2 | | ALL |
| 154 | 24 | PK | | | 3-2 | 27-51-11 | D06140P | | 5 | | | TB0176F | C093 | 2 | | ALL |
| 155 | 24 | PK | | | 3-2 | 27-51-11 | D06140P | | 6 | | | TB0176F | A094 | 2 | | ALL |
| 156 | 24 | PK | | | 3-2 | 27-51-11 | D06140P | | 7 | | | TB0176F | C094 | 2 | | ALL |
| 157 | 22 | PA | | | 4-10 | 27-81-11 | D05622P | | 50 | | | TB0176F | C106 | 2 | | ALL |
| 159 | 22 | PA | | | 3-1 | 27-81-21 | D05622P | | 51 | | | TB0176F | C097 | 2 | | ALL |
| 160 | 22 | PA | | | 4-10 | 27-51-11 | D05622P | | 27 | | | TB0176F | C105 | 2 | | ALL |
| 161 | 24 | PK | | | 3-11 | 24-51-52 | TB0176G | | 62 | 2 | | D05204P | 2 | | | 050-099 |
| 161 | 24 | PK | | | 3-10 | 24-51-52 | TB0176G | | 62 | 2 | | D05204P | 2 | | | 150-199 |
| 162 | 24 | PK | | | 2-11 | 24-51-52 | D05622P | | 53 | | | TB0176G | 62 | 2 | | 050-099 |
| 162 | 24 | PK | | | 2-10 | 24-51-52 | D05622P | | 53 | | | TB0176G | 62 | 2 | | 150-199 |
| 162 | 24 | PK | | | 3-2 | 24-51-52 | D05622P | | 53 | | | D05204P | 2 | | | 275-299 |
| 163 | 24 | PK | | | 3-11 | 24-51-52 | D05204P | | 3 | | | TB0176G | 63 | 2 | | 050-099 |
| 163 | 24 | PK | | | 3-10 | 24-51-52 | D05204P | | 3 | | | TB0176G | 63 | 2 | | 150-199 |
| 163 | 24 | PK | | | 3-6 | 24-51-52 | D05204P | | 3 | | | D04034P | 53 | | | 275-299 |
| 164 | 22 | PA | | | 3-11 | 24-51-52 | D05204P | | 4 | | | TB0176G | 63 | 2 | | 050-099 |
| 164 | 22 | PA | | | 3-10 | 24-51-52 | D05204P | | 4 | | | TB0176G | 63 | 2 | | 150-199 |
| 165 | 24 | PK | | | 4-3 | 24-51-52 | D04034P | | 53 | | | TB0176G | 63 | 2 | | 050-099 |
| 165 | 24 | PK | | | 3-2 | 24-51-52 | D04034P | | 53 | | | TB0176G | 63 | 2 | | 150-199 |
| 166 | 24 | PK | | | 5-5 | 24-51-71 | D04034P | | 18 | | | TB0176G | 1 | 2 | | ALL |
| 167 | 20 | PA | | | 4-1 | 25-31-11 | TB0176F | A051 | 2 | | | D04036P | 18 | DL | | 275-276 |
| 169 | 24 | PK | | | 2-11 | 24-11-21 | D00256A | D10 | | | | D04034P | 55 | | | ALL |
| 170 | 24 | PK | | | 4-4 | 31-51-21 | D05715P | | 22 | | | TB0176F | A012 | 2 | | 150-154, 275 |
| 171 | 24 | PK | | | 4-4 | 31-51-21 | D05715P | | 24 | | | TB0176F | C012 | 2 | | 150-154, 275 |
| 172 | 22 | PA | | | 2-8 | 27-81-11 | D05622P | | 54 | | | TB0176F | A080 | 2 | | ALL |
| 174 | 24 | PK | | | 5-1 | 24-11-21 | D04034P | | 20 | | | TB0176R | C139 | 2 | | ALL |
| 177 | 22 | PA | | | 3-1 | 27-81-11 | D05622P | | 55 | | | TB0176G | 95 | 2 | | ALL |
| 180 | 24 | PK | | | 3-11 | 24-11-21 | D00256A | A03 | | | | TB0176G | 41 | 2 | | 050-099 |
| 180 | 24 | PK | | | 3-9 | 24-11-21 | D00256A | A03 | | | | TB0176G | 41 | 2 | | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0010
Page 44
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|-------|---------|------|--------|-------|------|---------|--------|-------------|---|--|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0016 | 286T0016 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | | |
| 181 | 24 | | PK | 2-7 | 31-31-14 | D11788B | | D12 | | | | | D05715P | | 28 | | | ALL |
| 182 | 24 | | PK | 3-6 | 24-11-21 | D04916P | | 17 | | | | | TB0176G | 41 | 2 | | | 050-099 |
| 182 | 24 | | PK | 3-4 | 24-11-21 | D04916P | | 17 | | | | | TB0176G | 41 | 2 | | | 150-199, 275-299 |
| 183 | 24 | | PK | 2-6 | 24-11-21 | D04916P | | 18 | | | | | D00256A | | B03 | | | ALL |
| 187 | 24 | | PK | 3-1 | 77-35-11 | D05622P | | 41 | | | | | D11788C | | 2 | | | ALL |
| 188 | 24 | | PK | 3-0 | 77-35-11 | D11788C | | 4 | | | | | GD00012 | A.. | 2 | | | 050-099, 275-299 |
| 188 | 24 | | PK | 3-0 | 77-35-11 | D11788C | | 4 | | | | | GD00012 | D.. | 2 | | | 150-199 |
| 189 | 24 | | PK | 3-0 | 77-35-11 | D11788C | | 3 | | | | | GD00012 | S.. | 2 | | | ALL |
| 190 | 24 | | PK | 3-1 | 77-35-11 | D11788A | | B09 | | | | | D05622P | | 42 | | | 050-099 |
| 190 | 24 | | PK | 3-1 | 77-35-11 | D05622P | | 42 | | | | | D11788A | | B09 | | | 150-199, 275-299 |
| 191 | 24 | | PK | 3-8 | 77-35-11 | D11788A | | D13 | | | | | TB0176F | A177 | 2 | | | ALL |
| 192 | 24 | | PK | 3-0 | 77-35-11 | D11788A | | D14 | | | | | GD00012 | D.. | 2 | | | ALL |
| 193 | 20 | | PA | 2-9 | 73-21-14 | GD00012 | | S.. | 2 | | | | TB0176G | | 170 | 2 | | 050-099, 153-199, 275-299 |
| 193 | 20 | | PA | 2-9 | 73-21-14 | GD00012 | | S.. | 2 | | | | TB0176F | A170 | 2 | | | 150-152 |
| 194 | 20 | | PA | 2-11 | 73-21-14 | TB0176G | | 159 | 2 | | | | GD00012 | S.. | 2 | | | ALL |
| 201B | 24 | | PL | A | 4-11 | 27-51-11 | | D05622P | | 25 | | | TB0176F | A008 | 2 | | | ALL |
| 201R | 24 | | PL | A | 0-0 | 27-51-11 | | D05622P | | 26 | | | TB0176F | C008 | 2 | | | ALL |
| 202B | 24 | | PL | B | 4-10 | 27-81-11 | | D05622P | | 28 | | | TB0176F | A014 | 2 | | | ALL |
| 202R | 24 | | PL | B | 0-0 | 27-81-11 | | D05622P | | 29 | | | TB0176F | C013 | 2 | | | ALL |
| 203B | 24 | | PL | D | 4-9 | 27-81-21 | | D05622P | | 10 | | | TB0176F | A018 | 2 | | | ALL |
| 203R | 24 | | PL | D | 0-0 | 27-81-21 | | D05622P | | 11 | | | TB0176F | C018 | 2 | | | ALL |
| 204B | 24 | | PW | F | 6-2 | 21-31-21 | | D04768P | | 13 | | | TB0176F | C024 | 2 | | | ALL |
| 204R | 24 | | PW | F | 0-0 | 21-31-21 | | D04768P | | 14 | | | TB0176F | A025 | 2 | | | ALL |
| 204Z | | | | F | 0-0 | 21-31-21 | | D04768P | | 15 | | | TB0176F | C025 | 2 | | | ALL |
| 206B | 24 | | PW | H | 2-11 | 24-11-21 | | D00256A | | A04 | | | D04034P | | 1 | | | ALL |
| 206R | 24 | | PW | H | 0-0 | 24-11-21 | | D00256A | | B04 | | | D04034P | | 2 | | | ALL |
| 206Z | | | | H | 0-0 | 24-11-21 | | D00256A | | C11 | | | D04034P | | 3 | | | ALL |
| 207B | 24 | | PL | I | 2-11 | 24-11-21 | | D00256A | | A09 | | | D04034P | | 12 | | | ALL |
| 207R | 24 | | PL | I | 0-0 | 24-11-21 | | D00256A | | B09 | | | D04034P | | 13 | | | ALL |
| 208B | 24 | | PL | J | 2-11 | 24-11-21 | | D00256A | | D03 | | | D04034P | | 14 | | | ALL |
| 208R | 24 | | PL | J | 0-0 | 24-11-21 | | D00256A | | D01 | | | D04034P | | 15 | | | ALL |
| 209B | 22 | | PR | N | 2-11 | 24-21-21 | | D00256B | | A01 | | | D04034P | | 5 | | | ALL |
| 209R | 22 | | PR | N | 0-0 | 24-21-21 | | D00256B | | B01 | | | D04034P | | 6 | | | ALL |
| 209Z | | | | N | 0-0 | 24-21-21 | | D00256B | | C01 | | | D04034P | | 7 | | | ALL |
| 210B | 22 | | PR | Q | 4-2 | 24-22-22 | | D00256A | | B12 | | | TB0176F | A034 | 2 | | | ALL |
| 210R | 22 | | PR | Q | 0-0 | 24-22-22 | | D00256A | | A12 | | | TB0176F | C033 | 2 | | | ALL |
| 210Z | | | | Q | 0-0 | 24-22-22 | | D00256A | | B11 | | | TB0176F | C034 | 2 | | | ALL |
| 212B | 22 | | PR | BD | 2-4 | 29-11-31 | | D04078P | | 18 | | | D04916P | | 1 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 45

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0016 | 286T0016 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 212R | 22 | PR | BD | | 0-0 | 29-11-31 | D04078P | | 19 | | D04916P | | 13 | | ALL |
| 212Z | | | BD | | 0-0 | 29-11-31 | D04078P | DED | | | D04916P | DED | | | ALL |
| 216B | 20 | PR | Y | | 2-10 | 77-31-11 | D05622P | | 34 | | TB0176F | C076 | 2 | | ALL |
| 216R | 20 | PR | Y | | 0-0 | 77-31-11 | D05622P | | 33 | | TB0176F | A076 | 2 | | ALL |
| 216Z | | | Y | | 0-0 | 77-31-11 | D05622P | | 35 | | TB0176F | C075 | 2 | | ALL |
| 217B | 24 | PW | AA | | 2-10 | 21-31-21 | D05715P | | 7 | | TB0176G | 85 | 2 | | ALL |
| 217R | 24 | PW | AA | | 0-0 | 21-31-21 | D05715P | | 6 | | TB0176G | 86 | 2 | | ALL |
| 217Z | | | AA | | 0-0 | 21-31-21 | D05715P | | 5 | | TB0176F | A087 | 2 | | ALL |
| 220B | 24 | PW | AI | | 4-0 | 34-61-24 | D05715P | | 17 | | TB0176F | C128 | 2 | | ALL |
| 220R | 24 | PW | AI | | 0-0 | 34-61-24 | D05715P | | 16 | | TB0176F | A128 | 2 | | ALL |
| 220Z | | | AI | | 0-0 | 34-61-24 | D05715P | | 18 | | TB0176F | C028 | 2 | | ALL |
| 221B | 24 | PL | AJ | | 4-10 | 21-31-21 | D05204P | | 10 | | TB0176F | A129 | 2 | | ALL |
| 221R | 24 | PL | AJ | | 0-0 | 21-31-21 | D05204P | | 11 | | TB0176F | C129 | 2 | | ALL |
| 222B | 24 | PW | AP | | 2-10 | 73-21-14 | D05622P | | 36 | | TB0176G | 168 | 2 | | ALL |
| 222R | 24 | PW | AP | | 0-0 | 73-21-14 | D05622P | | 37 | | TB0176G | 169 | 2 | | ALL |
| 222Z | | | AP | | 0-0 | 73-21-14 | D05622P | | | FA | TB0176G | 170 | 2 | | 050-099, 153-199, 275-299 |
| 222Z | | | AP | | 0-0 | 73-21-14 | D05622P | | | FA | TB0176F | A170 | 2 | | 150-152 |
| 223B | 24 | PW | AQ | | 3-1 | 73-21-14 | D05622P | | 38 | | TB0176G | 160 | 2 | | ALL |
| 223R | 24 | PW | AQ | | 0-0 | 73-21-14 | D05622P | | 39 | | TB0176G | 161 | 2 | | ALL |
| 223Z | | | AQ | | 0-0 | 73-21-14 | D05622P | | | FA | TB0176G | 159 | 2 | | ALL |
| 224B | 24 | PW | AO | | 2-7 | 34-12-62 | D05715P | | 19 | | TB0176G | 160 | 2 | | ALL |
| 224R | 24 | PW | AO | | 0-0 | 34-12-62 | D05715P | | 20 | | TB0176G | 161 | 2 | | ALL |
| 224Z | | | AO | | 0-0 | 34-12-62 | D05715P | | 21 | | GDY0010 | S.. | 2 | | 050-099, 162-199, 277-299 |
| 224Z | | | AO | | 0-0 | 34-12-62 | D05715P | | 21 | | GDY0011 | S.. | 2 | | 150-157, 275-276 |
| 225B | 20 | PR | AG | | 6-5 | 21-31-21 | D04768P | | 10 | | TB0176F | A115 | 2 | | ALL |
| 225R | 20 | PR | AG | | 0-0 | 21-31-21 | D04768P | | 11 | | TB0176F | C115 | 2 | | ALL |
| 225Z | | | AG | | 0-0 | 21-31-21 | D04768P | DED | | | TB0176F | DED | | | ALL |
| 226 | 20 | UA | | | 1-6 | 31-31-14 | D11788B | | | JA | GDY0008 | S.. | 2 | | 050-099 |
| 226 | 20 | UA | | | 3-0 | 31-31-14 | D11788B | | | JA | GDY0012 | S.. | 2 | | 150-199, 275-299 |
| 226B | 24 | PW | JA | | 2-7 | 31-31-14 | D11788B | A15 | | | D05715P | 31 | | | ALL |
| 226R | 24 | PW | JA | | 0-0 | 31-31-14 | D11788B | A14 | | | D05715P | 30 | | | ALL |
| 226Z | | | JA | | 0-0 | 31-31-14 | D05715P | 29 | | | D11788B | | | JA | ALL |
| 227 | 20 | UA | | | 3-0 | 73-21-14 | D11788B | | | JB | GDY0012 | S.. | 2 | | ALL |
| 227B | 24 | PW | JB | | 3-1 | 73-21-14 | D11788B | B08 | | | D05622P | 43 | | | ALL |
| 227R | 24 | PW | JB | | 0-0 | 73-21-14 | D11788B | B07 | | | D05622P | 44 | | | ALL |
| 227Z | | | JB | | 0-0 | 73-21-14 | D11788B | | | JB | D05622P | 45 | | | ALL |
| 228B | 24 | PW | BJ | | 3-6 | 77-35-11 | D08614P | 4 | | | TB0176G | 175 | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0010
Page 46
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|----------|---------|---------|-------|------|------|---------|-------|------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0016 | 286T0016 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 228R | 24 | PW | BJ | 0-0 | 77-35-11 | D08614P | | 5 | | | TB0176G | 176 | 2 | | ALL |
| 228Z | | | BJ | 0-0 | 77-35-11 | D08614P | | 6 | | | GDY0011 | S.. | 2 | | ALL |
| 229B | 24 | PW | BK | 3-6 | 77-35-11 | D11788A | | D02 | | | TB0176G | 175 | 2 | | ALL |
| 229R | 24 | PW | BK | 0-0 | 77-35-11 | D11788A | | D01 | | | TB0176G | 176 | 2 | | ALL |
| 229Z | | | BK | 0-0 | 77-35-11 | D11788A | | DED | | | GDY0011 | S.. | 2 | | ALL |
| 230B | 24 | PW | BL | 3-6 | 77-35-11 | D08614P | | 1 | | | TB0176G | 173 | 2 | | ALL |
| 230R | 24 | PW | BL | 0-0 | 77-35-11 | D08614P | | 2 | | | TB0176G | 174 | 2 | | ALL |
| 230Z | | | BL | 0-0 | 77-35-11 | D08614P | | 3 | | | GDY0011 | S.. | 2 | | ALL |
| 231B | 24 | PW | BM | 3-6 | 77-35-11 | D11788B | | D02 | | | TB0176G | 173 | 2 | | ALL |
| 231R | 24 | PW | BM | 0-0 | 77-35-11 | D11788B | | D01 | | | TB0176G | 174 | 2 | | ALL |
| 231Z | | | BM | 0-0 | 77-35-11 | D11788B | | DED | | | GDY0011 | S.. | 2 | | ALL |
| 232 | 20 | UA | | 3-0 | 73-21-14 | D11788A | | | | JG | GDX0012 | S.. | 2 | | ALL |
| 232B | 24 | PW | JG | 3-3 | 73-21-14 | D11788A | | C12 | | | D06140P | 12 | | | ALL |
| 232R | 24 | PW | JG | 0-0 | 73-21-14 | D11788A | | C11 | | | D06140P | 13 | | | ALL |
| 232Z | | | JG | 0-0 | 73-21-14 | D11788A | | | | JG | D06140P | 14 | | | ALL |
| 233B | 24 | PW | BN | 2-6 | 22-33-11 | D05715P | | 26 | | | TB0176G | 175 | 2 | | ALL |
| 233R | 24 | PW | BN | 0-0 | 22-33-11 | D05715P | | 25 | | | TB0176G | 176 | 2 | | ALL |
| 233Z | | | BN | 0-0 | 22-33-11 | D05715P | | 27 | | | GDY0011 | S.. | 2 | | ALL |
| 234B | 24 | PW | BP | 2-6 | 22-33-11 | D05715P | | 33 | | | TB0176G | 173 | 2 | | ALL |
| 234R | 24 | PW | BP | 0-0 | 22-33-11 | D05715P | | 32 | | | TB0176G | 174 | 2 | | ALL |
| 234Z | | | BP | 0-0 | 22-33-11 | D05715P | | 34 | | | GDY0011 | S.. | 2 | | ALL |
| 235B | 24 | PW | JJ | 3-7 | 28-41-11 | D08614P | | 9 | | | TB0176G | 166 | 2 | | ALL |
| 235R | 24 | PW | JJ | 0-0 | 28-41-11 | D08614P | | 8 | | | TB0176G | 165 | 2 | | ALL |
| 235Z | | | JJ | 0-0 | 28-41-11 | D08614P | | 7 | | | GDY0010 | S.. | 2 | | 050-099, 162-199, 277-299 |
| 235Z | | | JJ | 0-0 | 28-41-11 | D08614P | | 7 | | | GDY0011 | S.. | 2 | | 150-157, 275-276 |
| 243B | 22 | PR | JR | 3-11 | 31-31-22 | D08614P | | 11 | | | TB0176X | A058 | BJ | | ALL |
| 243R | 22 | PR | JR | 0-0 | 31-31-22 | D08614P | | 10 | | | TB0176X | A057 | BJ | | ALL |
| 243Z | | | JR | 0-0 | 31-31-22 | D08614P | | 12 | | | GDY0009 | S.. | 2 | | ALL |
| 247B | 24 | PW | AT | 3-7 | 77-31-11 | D06140P | | 19 | | | TB0176F | A142 | 2 | | ALL |
| 247R | 24 | PW | AT | 0-0 | 77-31-11 | D06140P | | 18 | | | TB0176F | C141 | 2 | | ALL |
| 247Z | | | AT | 0-0 | 77-31-11 | D06140P | | 20 | | | TB0176F | C143 | 2 | | ALL |
| 249B | 24 | PW | AU | 3-7 | 77-31-11 | D06140P | | 22 | | | TB0176F | A143 | 2 | | ALL |
| 249R | 24 | PW | AU | 0-0 | 77-31-11 | D06140P | | 21 | | | TB0176F | C142 | 2 | | ALL |
| 249Z | | | AU | 0-0 | 77-31-11 | D06140P | | 23 | | | TB0176F | A145 | 2 | | ALL |
| 301B | 18 | PC | P | 3-3 | 24-21-21 | D00256C | | 2 | | | D04036P | 1 | | | ALL |
| 301R | 18 | PC | P | 0-0 | 24-21-21 | D00256C | | 3 | | | D04036P | 2 | | | ALL |
| 301Y | 18 | PC | P | 0-0 | 24-21-21 | D00256C | | 4 | | | D04036P | 3 | | | ALL |
| 303B | 24 | PM | C | 4-10 | 27-81-11 | D05622P | | 30 | | | TB0176F | A015 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 47

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0016 | 286T0016 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 303R | 24 | PM | C | | 0-0 | 27-81-11 | D05622P | | 31 | | | TB0176F | C014 | 2 | | ALL |
| 303Y | 24 | PM | C | | 0-0 | 27-81-11 | D05622P | | 32 | | | TB0176F | C015 | 2 | | ALL |
| 304B | 24 | PM | E | | 4-9 | 27-81-21 | D05622P | | 12 | | | TB0176F | A019 | 2 | | ALL |
| 304R | 24 | PM | E | | 0-0 | 27-81-21 | D05622P | | 13 | | | TB0176F | C019 | 2 | | ALL |
| 304Y | 24 | PM | E | | 0-0 | 27-81-21 | D05622P | | 14 | | | TB0176F | A020 | 2 | | ALL |
| 305B | 18 | PS | AB | | 3-0 | 24-21-21 | D04036P | | 9 | | | SM00001 | | W | | ALL |
| 305R | 18 | PS | AB | | 0-0 | 24-21-21 | D04036P | | 10 | | | SM00002 | | W | | ALL |
| 305Y | 18 | PS | AB | | 0-0 | 24-21-21 | D04036P | | 11 | | | SM00003 | | W | | ALL |
| 305Z | | | AB | | 0-0 | 24-21-21 | D04036P | DED | | | | SM00003 | DED | | | ALL |
| 401B | 24 | PN | O | | 2-11 | 24-21-21 | D00256B | | A13 | | | D04034P | | 8 | | ALL |
| 401G | 24 | PN | O | | 0-0 | 24-21-21 | D00256B | | D13 | | | D04034P | | 11 | | ALL |
| 401R | 24 | PN | O | | 0-0 | 24-21-21 | D00256B | | B13 | | | D04034P | | 9 | | ALL |
| 401Y | 24 | PN | O | | 0-0 | 24-21-21 | D00256B | | C13 | | | D04034P | | 10 | | ALL |
| 402B | 24 | PN | K | | 3-0 | 24-23-11 | D00256B | | A11 | | | D04078P | | 1 | | ALL |
| 402G | 24 | PN | K | | 0-0 | 24-23-11 | D00256B | | D11 | | | D04078P | | 4 | | ALL |
| 402R | 24 | PN | K | | 0-0 | 24-23-11 | D00256B | | B11 | | | D04078P | | 2 | | ALL |
| 402Y | 24 | PN | K | | 0-0 | 24-23-11 | D00256B | | C11 | | | D04078P | | 3 | | ALL |
| 403B | 24 | PN | L | | 3-0 | 24-23-11 | D00256B | | A10 | | | D04078P | | 5 | | ALL |
| 403G | 24 | PN | L | | 0-0 | 24-23-11 | D00256B | | D10 | | | D04078P | | 8 | | ALL |
| 403R | 24 | PN | L | | 0-0 | 24-23-11 | D00256B | | B10 | | | D04078P | | 6 | | ALL |
| 403Y | 24 | PN | L | | 0-0 | 24-23-11 | D00256B | | C10 | | | D04078P | | 7 | | ALL |
| 404B | 24 | PN | M | | 3-0 | 24-23-11 | D00256B | | A12 | | | D04078P | | 9 | | ALL |
| 404G | 24 | PN | M | | 0-0 | 24-23-11 | D00256B | | D12 | | | D04078P | | 12 | | ALL |
| 404R | 24 | PN | M | | 0-0 | 24-23-11 | D00256B | | B12 | | | D04078P | | 10 | | ALL |
| 404Y | 24 | PN | M | | 0-0 | 24-23-11 | D00256B | | C12 | | | D04078P | | 11 | | ALL |
| 451G | 22 | XU | AM | | 3-0 | 32-46-11 | D05292P | | 6 | 4F | | TB0176F | C088 | 2 | | ALL |
| 451W | 22 | XU | AM | | 0-0 | 32-46-11 | D05292P | | 5 | 4J | | TB0176F | A088 | 2 | | ALL |
| 452G | 22 | XU | AN | | 3-0 | 32-46-11 | D05292P | | 8 | 4F | | TB0176F | C089 | 2 | | ALL |
| 452W | 22 | XU | AN | | 0-0 | 32-46-11 | D05292P | | 7 | 4J | | TB0176F | A089 | 2 | | ALL |
| 453G | 22 | XU | AR | | 4-0 | 32-46-11 | D05292P | | 2 | 4F | | TB0176F | C131 | 2 | | ALL |
| 453W | 22 | XU | AR | | 0-0 | 32-46-11 | D05292P | | 1 | 4J | | TB0176F | A131 | 2 | | ALL |
| 454G | 22 | XU | AS | | 3-0 | 32-46-11 | D05292P | | 4 | 4F | | TB0176F | C072 | 2 | | 050-099 |
| 454G | 22 | XU | AS | | 3-1 | 32-46-11 | D05292P | | 4 | 4F | | TB0176F | C072 | 2 | | 150-199, 275-299 |
| 454W | 22 | XU | AS | | 0-0 | 32-46-11 | D05292P | | 3 | 4J | | TB0176F | A072 | 2 | | ALL |
| 501 | 24 | PV | UA | | 3-1 | 73-21-17 | D05622P | | 47 | | | D11788A | A11 | | | ALL |
| 501Z | | | UA | | 0-0 | 73-21-17 | D05622P | | | | FJ | D11788A | | | FK | ALL |
| 502 | 24 | PV | UB | | 3-1 | 73-21-17 | D05622P | | 48 | | | D11788A | A10 | | | ALL |
| 502Z | | | UB | | 0-0 | 73-21-17 | D05622P | | | | FJ | D11788A | | | FK | ALL |
| 503 | 20 | UA | | | 3-4 | 73-21-17 | GDY0011 | | S.. | 2 | | D11788A | | | FK | ALL |

WIRE LIST
D280T132

91-21-11
Section W0010
Page 48
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0016 | 286T0016 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | |
| 504 | 22 | | PA | 3-11 | 31-31-22 | D08614P | | 13 | | | | | TB0176F | A059 | 2 | | ALL |
| 505 | 24 | | PK | 4-3 | 31-31-26 | TB0176F | | C020 | 2 | | | | D05715P | 35 | | | ALL |
| 506 | 24 | | PK | 3-0 | 31-31-26 | D04036P | | 14 | | | | | D05715P | 36 | | | ALL |
| 507 | 24 | | PV | 3-0 | 31-31-26 | D04036P | | 15 | | | | | D05715P | 37 | | | ALL |
| 507Z | | | | 0-0 | 31-31-26 | D04036P | | DED | | | | | D05715P | DED | | | ALL |
| 509 | 24 | | PK | 4-4 | 27-81-31 | TB0176F | | C016 | 2 | | | | D05715P | 3 | | | ALL |
| 511 | 24 | | PK | 4-0 | 24-11-21 | D00256A | | D13 | | | | | D04078P | 21 | | | ALL |
| 513 | 22 | | PA | 1-0 | 29-33-11 | D02704B | | A06 | | | | | GDZ0001 | S.. | E | * | ALL |
| 515 | 24 | | PK | 6-0 | 27-51-61 | M02189 | | A | D | | | | TB0176F | A003 | 2 | | 050-099 |
| 515 | 24 | | PK | 4-10 | 27-51-61 | M02189 | | A | D | | | | TB0176F | A003 | 2 | | 150-199, 275-299 |
| FRA | | | | 0-0 | 73-21-14 | D05622P | | | | | FA | | D05622P | 40 | | | ALL |
| FRB | | | | 0-0 | 29-33-11 | D04916P | | | | | FD | | D04916P | 4 | | | ALL |
| FRC | | | | 0-0 | 29-33-11 | D04916P | | | | | FD | | D04916P | 14 | | | ALL |
| FRD | | | | 0-0 | 29-33-11 | D04916P | | | | | FD | | D04916P | 5 | | | ALL |
| FRE | | | | 0-0 | 29-33-11 | D02704B | | | | | FN | | GDZ0001 | S.. | E | * | ALL |
| FRG | | | | 0-0 | 29-33-11 | D02704B | | | | | FN | | D02704B | B06 | | | ALL |
| FRI | | | | 0-0 | 29-33-11 | D02704B | | | | | FN | | D02704B | C06 | | | ALL |
| FRJ | | | | 0-0 | 73-21-17 | D05622P | | | | | FJ | | D05622P | 46 | | | 050-099, 150-199, 277-299 |
| W0017 | 286T0017 | | | P1-1 CAPT INSTR PNL-L | | | | | | | | | | | | | |
| 001 | 24 | | PK | 1-11 | 34-22-82 | D04283J | | 4 | | | | | S00004 | 2 | 1A | | ALL |
| 002 | 20 | | PA | 1-11 | 34-22-82 | D04283J | | 5 | | | | | S00004 | 3 | 1A | | ALL |
| 003 | 24 | | PK | 1-11 | 34-22-17 | D04283J | | 11 | | | | | S00004 | 6 | 1A | | ALL |
| 004 | 20 | | PA | 1-11 | 34-22-17 | D04283J | | 12 | | | | | S00004 | 5 | 1A | | ALL |
| 005 | 24 | | PK | 1-11 | 34-22-17 | D04283J | | 13 | | | | | S00001 | B | 1A | | ALL |
| 006 | 24 | | PK | 1-11 | 34-22-17 | D04283J | | 14 | | | | | S00001 | D | 1A | | ALL |
| 007 | 20 | | PA | 1-11 | 34-22-17 | D04283J | | 15 | | | | | S00001 | A | 1A | | ALL |
| 008 | 22 | | PA | 1-10 | 34-22-17 | D04283J | | 16 | | | | | S00003 | 5 | 1A | | ALL |
| 009 | 20 | | PA | 1-10 | 34-22-17 | D04283J | | 21 | | | | | S00003 | 6 | 1A | | ALL |
| 010 | 20 | | PA | 1-10 | 34-22-17 | D04283J | | 10 | | | | | S00002 | BB | 1A | | 050, 150-154, 275-276 |
| 010 | 20 | | PA | 1-10 | 34-22-17 | D04283J | | 10 | | | | | S00002 | AB | 1A | | 051-099, 155-199, 277-299 |
| 011 | 24 | | PK | 1-10 | 34-22-17 | D04283J | | 9 | | | | | S00002 | BA | 1A | | 050, 150-154, 275-276 |
| 011 | 24 | | PK | 1-10 | 34-22-17 | D04283J | | 9 | | | | | S00002 | AA | 1A | | 051-099, 155-199, 277-299 |
| 012 | 24 | | PK | 1-10 | 34-22-38 | D04283J | | 6 | | | | | S00003 | 1 | 1A | | ALL |
| 013 | 24 | | PK | 2-1 | 34-22-38 | D04287J | | 2 | | | | | S00003 | 3 | 1A | | ALL |
| 014 | 24 | | PK | 1-10 | 34-22-37 | D04283J | | 7 | | | | | S00003 | 7 | 1A | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 49

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0017 | 286T0017 | | | P1-1 CAPT INSTR PNL-L (continued) | | | | | | | | | | | | | |
| 015 | 20 | PA | | | 1-10 | 34-22-37 | D04283J | | 8 | | | | S00003 | 9 | 1A | | ALL |
| 016 | 24 | PK | | | 1-11 | 34-22-91 | D04283J | | 18 | | | | S00004 | 9 | 1A | | ALL |
| 017 | 20 | PA | | | 1-11 | 34-22-91 | D04283J | | 19 | | | | S00004 | 8 | 1A | | ALL |
| 025 | 22 | PA | | | 1-11 | 34-12-61 | S00482 | | 8 | 1A | | | D04283J | 36 | | | ALL |
| 026 | 18 | PA | | | 1-3 | 33-13-11 | D04283J | | 22 | DL | | | SM00003 | | W | | ALL |
| 027 | 18 | PA | | | 1-3 | 33-13-11 | D04283J | | 23 | DL | | | SM00004 | | W | | ALL |
| 029 | 22 | PA | | | 1-10 | 34-22-38 | D04283J | | 20 | | | | S00003 | 2 | 1A | | ALL |
| 030 | 20 | PA | | | 1-11 | 34-12-61 | D04283J | | 24 | | | | S00482 | 6 | 1A | | ALL |
| 031 | 22 | PA | | | 1-11 | 34-12-61 | D04283J | | 25 | | | | S00482 | 9 | 1A | | ALL |
| 032 | 20 | PA | | | 1-11 | 34-12-61 | D04283J | | 26 | | | | S00482 | 3 | 1A | | ALL |
| 036 | 22 | PA | | | 1-11 | 34-12-61 | D04283J | | 30 | | | | S00482 | 5 | 1A | | ALL |
| 037 | 22 | PA | | | 1-11 | 34-13-11 | D04283J | | 31 | | | | S00482 | 2 | 1A | | ALL |
| 039 | 24 | PK | | | 1-11 | 22-41-13 | D04283J | | 38 | | | | S00001 | G | 1A | | ALL |
| 040 | 24 | PK | | | 1-11 | 22-41-13 | D04283J | | 37 | | | | S00001 | H | 1A | | ALL |
| 041 | 24 | PK | | | 2-2 | 22-41-13 | D04287J | | 1 | | | | S00001 | J | 1A | | ALL |
| 042 | 24 | PK | | | 1-11 | 22-41-13 | D04283J | | 39 | | | | S00001 | F | 1A | | ALL |
| 043 | 22 | PA | | | 1-10 | 34-22-16 | D04283J | | 32 | | | | S00003 | 12 | 1A | | ALL |
| 044 | 20 | PA | | | 1-10 | 34-22-16 | D04283J | | 33 | | | | S00003 | 11 | 1A | | ALL |
| 046 | 20 | PA | | | 1-10 | 34-22-17 | D04283J | | 27 | | | | S00002 | BD | 1A | | 050, 150-154, 275-276 |
| 046 | 20 | PA | | | 1-10 | 34-22-17 | D04283J | | 27 | | | | S00002 | AD | 1A | | 051-099, 155-199, 277-299 |
| 047 | 20 | PA | | | 1-7 | 33-13-11 | SM00003 | | | W | | | L00481 | =P | B | | ALL |
| 048 | 20 | PA | | | 1-3 | 33-13-11 | SM00003 | | | W | | | S00482 | 13 | 1A | | ALL |
| 050 | 20 | PA | | | 1-1 | 33-13-11 | SM00003 | | | W | | | S00003 | 13 | 1A | | ALL |
| 051 | 20 | PA | | | 1-2 | 33-13-11 | SM00003 | | | W | | | S00004 | 13 | 1A | | ALL |
| 052 | 20 | PA | | | 1-7 | 33-13-11 | SM00004 | | | W | | | GDX0001 | A.. | E | | ALL |
| 053 | 20 | PA | | | 1-3 | 33-13-11 | SM00004 | | | W | | | S00482 | 15 | 1A | | ALL |
| 055 | 20 | PA | | | 1-1 | 33-13-11 | SM00004 | | | W | | | S00003 | 15 | 1A | | ALL |
| 056 | 20 | PA | | | 1-2 | 33-13-11 | SM00004 | | | W | | | S00004 | 15 | 1A | | ALL |
| 057 | 24 | PK | | | 1-11 | 32-42-11 | D04283J | | 2 | | | | S00004 | 11 | 1A | | ALL |
| 058 | 24 | PK | | | 1-11 | 32-42-11 | D04283J | | 1 | | | | S00004 | 12 | 1A | | ALL |
| 059 | 24 | PK | | | 1-10 | 34-22-17 | D04283J | | 17 | | | | S00003 | 8 | 1A | | ALL |
| 064 | 20 | PA | | | 1-10 | 34-61-16 | S00002 | | AA | 1A | | | D04283J | 3 | | | 050, 150-154 |
| 066 | 20 | PA | | | 1-10 | 34-61-16 | S00002 | | AB | 1A | | | D04283J | 34 | | | 050, 150-154 |
| 067 | 20 | PA | | | 1-10 | 34-61-16 | S00002 | | AD | 1A | | | D04283J | 51 | | | 050, 150-154 |
| 068 | 20 | PA | | | 1-10 | 34-61-16 | S00002 | | AG | 1A | | | D04283J | 52 | | | 050, 150-154 |
| 069 | 20 | PA | | | 1-10 | 34-61-16 | S00002 | | AF | 1A | | | D04283J | 53 | | | 050, 150-154 |
| 070 | 20 | PA | | | 1-10 | 34-61-16 | S00002 | | BJ | 1A | | | D04283J | 54 | | | ALL |
| 071 | 20 | PA | | | 1-10 | 34-61-16 | S00002 | | BF | 1A | | | D04283J | 55 | | | 050, 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 50

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0017 | 286T0017 | | | P1-1 CAPT INSTR PNL-L (continued) | | | | | | | | | | | | |
| 072 | 20 | PA | | 1-10 | 34-61-16 | S00002 | AH | 1A | | D04283J | 3 | | | 051-099, 155-199, 275-299 | | |
| 073 | 20 | PA | | 1-10 | 34-61-16 | S00002 | AK | 1A | | D04283J | 34 | | | 051-099, 155-199, 275-299 | | |
| 074 | 20 | PA | | 1-10 | 34-61-16 | S00002 | AJ | 1A | | D04283J | 51 | | | 051-099, 155-199, 275-299 | | |
| 075 | 20 | PA | | 1-10 | 34-61-16 | S00002 | AF | 1A | | D04283J | 52 | | | 051-099, 155-199, 275-299 | | |
| 076 | 20 | PA | | 1-10 | 34-61-16 | S00002 | AE | 1A | | D04283J | 53 | | | 051-099, 155-199, 275-299 | | |
| 077 | 20 | PA | | 1-10 | 34-61-16 | S00002 | BH | 1A | | D04283J | 55 | | | 051-099, 155-199, 275-299 | | |
| 078 | 20 | PA | | 1-10 | 34-61-16 | S00002 | BE | 1A | | D04283J | 28 | | | 051-099, 155-199, 275-299 | | |
| 079 | 20 | PA | | 1-10 | 34-61-16 | S00002 | BF | 1A | | D04283J | 48 | | | 051-099, 155-199, 275-299 | | |
| 080 | 20 | PA | | 1-10 | 34-61-16 | S00002 | BG | 1A | | D04283J | 49 | | | 051-099, 155-199, 275-299 | | |
| 081 | 20 | PA | | 2-1 | 34-61-16 | S00002 | BA | 1A | | D04287J | 5 | | | 051-099, 155-199, 277-299 | | |
| 081 | 20 | PA | | 2-1 | 34-61-16 | S00002 | AA | 1A | | D04287J | 5 | | | 275-276 | | |
| 082 | 20 | PA | | 2-1 | 34-61-16 | S00002 | BB | 1A | | D04287J | 6 | | | 051-099, 155-199, 277-299 | | |
| 082 | 20 | PA | | 2-1 | 34-61-16 | S00002 | AB | 1A | | D04287J | 6 | | | 275-276 | | |
| 083 | 20 | PA | | 2-1 | 34-61-16 | S00002 | BC | 1A | | D04287J | 7 | | | 051-099, 155-199, 277-299 | | |
| 083 | 20 | PA | | 2-1 | 34-61-16 | S00002 | AC | 1A | | D04287J | 7 | | | 275-276 | | |
| 104 | 22 | PA | | 2-6 | 34-12-61 | D04283J | | | 40 | S00482 | 12 | 1A | | ALL | | |
| 105 | 22 | PA | | 2-6 | 34-12-61 | D04283J | | | 42 | S00482 | 10 | 1A | | ALL | | |
| 106 | 22 | PA | | 2-6 | 34-12-61 | D04283J | | | 43 | S00482 | 11 | 1A | | ALL | | |
| 913 | 20 | PA | | 12-0 | 33-13-11 | SPZ0002 | | | | D09131 | 22 | | | 150, 152-199, 275-299 | | |
| 914 | 20 | PA | | 12-0 | 33-13-11 | GD03702 | A.. | 2 | | D09131 | 23 | | | 150, 152-199, 275-299 | | |
| W0018 | 286T0018 | | | SHELF E2-4 INTEGRATION BUNDLE | | | | | | | | | | | | |
| 001 | 24 | PK | | 6-9 | 24-51-71 | D04072P | | | 32 | D04048P | 23 | | | ALL | | |
| 002 | 24 | PK | | 5-5 | 24-22-12 | D00278A | | | A03 | TB0176F | C027 | 2 | | ALL | | |
| 003 | 24 | PK | | 5-5 | 24-22-12 | D00278A | | | B04 | TB0176F | A028 | 2 | | ALL | | |
| 004 | 24 | PK | | 4-9 | 24-22-22 | D00278A | | | C03 | TB0176F | A032 | 2 | | ALL | | |
| 005 | 24 | PK | | 4-9 | 24-22-22 | D00278A | | | B03 | TB0176F | C032 | 2 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 51

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0018 | 286T0018 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 006 | 24 | | PK | | 4-9 | 24-22-22 | D00278A | | C04 | | TB0176F | A033 | 2 | | ALL |
| 007 | 24 | | PK | | 3-7 | 24-22-41 | D04072P | | 12 | | D00264A | A01 | | | ALL |
| 008 | 24 | | PK | | 6-0 | 24-22-41 | D04048P | | 1 | | D00264A | B05 | | | ALL |
| 009 | 20 | | PA | | 6-5 | 24-22-41 | D04048P | | 10 | | TB0176G | 71 | 2 | | ALL |
| 010 | 20 | | PA | | 6-5 | 24-22-41 | D04048P | | 27 | | TB0176G | 71 | 2 | | ALL |
| 011 | 24 | | PK | | 6-0 | 24-22-41 | D04048P | | 2 | | D00264A | C02 | | | ALL |
| 012 | 24 | | PK | | 6-0 | 24-22-41 | D04048P | | 40 | | D00264A | A05 | | | ALL |
| 013 | 24 | | PK | | 6-0 | 24-22-41 | D04048P | | 16 | | D00264A | D06 | | | ALL |
| 014 | 24 | | PK | | 3-7 | 24-22-41 | D04072P | | 22 | | D00264A | A06 | | | ALL |
| 015 | 24 | | PK | | 6-8 | 24-41-11 | D04048P | | 21 | | D00278B | A07 | | | ALL |
| 016 | 24 | | PK | | 6-8 | 24-41-11 | D04048P | | 20 | | D00278B | B07 | | | ALL |
| 017 | 24 | | PK | | 6-8 | 24-41-11 | D04048P | | 19 | | D00278B | C07 | | | ALL |
| 018 | 24 | | PK | | 2-11 | 24-41-11 | D04072P | | 19 | | D00278B | A02 | | | ALL |
| 019 | 24 | | PK | | 2-11 | 24-41-11 | D04072P | | 20 | | D00278B | B02 | | | ALL |
| 020 | 24 | | PK | | 6-8 | 24-41-11 | D04048P | | 18 | | D00278A | D03 | | | ALL |
| 021 | 24 | | PK | | 6-8 | 24-41-11 | D04048P | | 17 | | D00278A | A04 | | | ALL |
| 022 | 24 | | PK | | 6-1 | 24-27-21 | D04072P | | 18 | | TB0176F | A024 | 2 | | ALL |
| 023 | 24 | | PK | | 4-10 | 24-27-21 | D04048P | | 24 | | TB0176F | A030 | 2 | | ALL |
| 024 | 24 | | PK | | 4-2 | 24-51-71 | D00278B | | A10 | | TB0176G | 61 | 2 | | ALL |
| 025 | 24 | | PK | | 4-10 | 24-28-21 | D05206P | | 3 | | TB0176G | 162 | 2 | | ALL |
| 026 | 24 | | PK | | 4-10 | 24-28-21 | D05206P | | 4 | | TB0176G | 163 | 2 | | ALL |
| 027 | 24 | | PK | | 4-10 | 24-28-21 | D05206P | | 5 | | TB0176G | 164 | 2 | | ALL |
| 028 | 24 | | PK | | 3-5 | 24-28-21 | D00264A | | A10 | | TB0176G | 162 | 2 | | ALL |
| 029 | 24 | | PK | | 2-11 | 24-41-12 | D04072P | | 21 | | D00278B | A03 | | | ALL |
| 030 | 24 | | PK | | 3-5 | 24-28-21 | D00264A | | B02 | | TB0176G | 162 | 2 | | ALL |
| 031 | 24 | | PK | | 6-9 | 24-51-71 | D04072P | | 33 | | D04048P | 22 | | | ALL |
| 032 | 24 | | PK | | 3-10 | 24-51-71 | D04048P | | 45 | | TB0176G | 1 | 2 | | ALL |
| 033 | 24 | | PK | | 3-10 | 24-51-71 | D04048P | | 46 | | TB0176G | 1 | 2 | | ALL |
| 034 | 24 | | PK | | 3-8 | 24-27-11 | D04072P | | 17 | | TB0176F | C084 | 2 | | ALL |
| 035 | 22 | | PA | | 6-3 | 33-16-22 | D00278B | | D03 | | TB0176F | A110 | 2 | | ALL |
| 036 | 22 | | PA | | 0-6 | 24-21-41 | D00264B | | A15 | | SM00001 | | W | | ALL |
| 037 | 22 | | PA | | 0-6 | 24-21-41 | D00264B | | B15 | | SM00002 | | W | | ALL |
| 038 | 22 | | PA | | 0-6 | 24-21-41 | D00264B | | C15 | | SM00003 | | W | | ALL |
| 039 | 22 | | PQ | R | 6-0 | 24-22-41 | D00264B | | A03 | | D04048P | 8 | | | ALL |
| 039Z | | | | R | 0-0 | 24-22-41 | D00264B | | DED | | D04048P | DED | | | ALL |
| 040 | 22 | | PA | | 6-0 | 24-22-41 | D00264B | | D02 | | D04048P | 9 | | | ALL |
| 041 | 22 | | PA | | 3-3 | 24-22-41 | D00264A | | C05 | | TB0176G | 71 | 2 | | ALL |
| 042 | 22 | | PA | | 6-0 | 24-22-41 | D00264A | | B01 | | D04048P | 26 | | | ALL |
| 043 | 22 | | PA | | 6-0 | 24-22-41 | D00264A | | C01 | | D04048P | 25 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0010
Page 52
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|---------|-------|------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0018 | 286T0018 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 044 | 18 | PQ | X | | 4-10 | 24-22-41 | D04114P | | 1 | | SM00004 | | W | | ALL |
| 044Z | | | X | | 0-0 | 24-22-41 | D04114P | | DED | | SM00004 | DED | | | ALL |
| 045 | 22 | PA | | | 0-6 | 24-22-41 | D00264A | | C15 | | SM00004 | | W | | ALL |
| 046 | 22 | PA | | | 2-10 | 24-22-41 | D00264A | | A11 | | GDX0008 | D.. | 2 | | ALL |
| 047 | 24 | PK | | | 6-8 | 24-41-11 | D04048P | | 11 | | D00278A | B10 | | | ALL |
| 048 | 22 | PA | | | 1-2 | 24-41-11 | SM00006 | | | W | D00278B | B01 | | | ALL |
| 049 | 20 | PQ | T | | 6-8 | 24-41-11 | D04048P | | 12 | | D00278C | | 3 | | ALL |
| 049Z | | | T | | 0-0 | 24-41-11 | D04048P | | DED | | D00278C | DED | | | ALL |
| 050 | 22 | PA | | | 3-6 | 24-41-11 | D00278B | | B08 | | GDX0008 | D.. | 2 | | 050-099, 150-199, 275-276 |
| 050 | 22 | PA | | | 3-4 | 24-41-11 | D00278B | | B08 | | GDX0009 | D.. | 2 | | 277-299 |
| 051 | 22 | PA | | | 3-6 | 24-41-11 | D00278B | | D08 | | GDX0008 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 051 | 22 | PA | | | 3-4 | 24-41-11 | D00278B | | D08 | | GDX0009 | S.. | 2 | | 277-299 |
| 052 | 22 | PA | | | 6-8 | 24-41-11 | D00278B | | A12 | | D04048P | | 28 | | ALL |
| 053 | 24 | PK | | | 6-2 | 24-22-12 | D04072P | | 25 | | TB0176F | C120 | 2 | | ALL |
| 054 | 20 | PA | | | 6-2 | 24-22-12 | D04072P | | 23 | | TB0176F | A120 | 2 | | ALL |
| 055 | 24 | PK | | | 6-2 | 24-51-31 | D04072P | | 28 | | TB0176F | C119 | 2 | | ALL |
| 056 | 24 | PK | | | 6-2 | 24-22-12 | D04072P | | 24 | | TB0176F | A119 | 2 | | ALL |
| 057 | 24 | PK | | | 6-2 | 24-51-31 | D04072P | | 27 | | TB0176F | C118 | 2 | | ALL |
| 058 | 20 | PA | | | 6-2 | 24-22-12 | D04072P | | 26 | | TB0176F | A118 | 2 | | ALL |
| 059 | 20 | PA | | | 3-9 | 24-22-22 | D04048P | | 48 | | TB0176F | A103 | 2 | | ALL |
| 060 | 20 | PA | | | 3-9 | 24-22-22 | D04048P | | 49 | | TB0176F | A101 | 2 | | ALL |
| 061 | 24 | PK | | | 6-0 | 24-41-11 | D04048P | | 52 | | D00264A | D07 | | | ALL |
| 062 | 20 | PQ | U | | 6-0 | 24-41-11 | D04048P | | 13 | | SM00006 | | W | | ALL |
| 062Z | | | U | | 0-0 | 24-41-11 | D04048P | | DED | | SM00006 | DED | | | ALL |
| 063 | 24 | PK | | | 4-1 | 24-28-21 | D00278A | | D04 | | TB0176G | 163 | 2 | | ALL |
| 064 | 22 | PQ | O | | 6-3 | 24-51-13 | D00278B | | B14 | | TB0176F | A109 | 2 | | ALL |
| 064Z | | | O | | 0-0 | 24-51-13 | D00278B | | DED | | TB0176F | DED | | | ALL |
| 066 | 24 | PV | W | | 5-4 | 24-51-23 | D00278B | | C14 | | TB0176F | A121 | 2 | | ALL |
| 066Z | | | W | | 0-0 | 24-51-23 | D00278B | | DED | | TB0176F | DED | | | ALL |
| 068 | 22 | PA | | | 4-9 | 25-31-11 | D00278A | | D09 | | TB0176G | 37 | 2 | | ALL |
| 069 | 22 | PA | | | 4-9 | 25-31-11 | D00278B | | C12 | | TB0176F | A038 | 2 | | ALL |
| 071 | 24 | PK | | | 4-10 | 24-51-71 | D04048P | | 3 | | TB0176F | A039 | 2 | | ALL |
| 072 | 22 | PA | | | 3-8 | 25-31-21 | D00278B | | B12 | | TB0176G | 172 | 2 | | 050-099, 150-199 |
| 073 | 22 | PA | | | 3-8 | 25-31-21 | D00278A | | C09 | | TB0176G | 171 | 2 | | 050-099, 150-199, 275-278 |
| 073 | 22 | PA | | | 4-9 | 25-31-21 | D00278A | | C09 | | TB0176F | C036 | 2 | | 280-299 |
| 074 | 24 | PK | | | 6-0 | 24-51-71 | D04048P | | 6 | | TB0176F | C059 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 53

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0018 | 286T0018 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 077 | 24 | | PK | | 6-8 | 24-51-51 | D00278B | D11 | | | D04048P | 31 | | | ALL |
| 078 | 24 | | PK | | 4-5 | 24-51-51 | D00278B | C11 | | | TB0176G | 144 | 2 | | ALL |
| 079 | 24 | | PK | | 3-7 | 24-41-11 | D00278B | A01 | | | TB0176G | 81 | 2 | | ALL |
| 080 | 22 | | PA | | 5-4 | 24-51-51 | D00278A | C10 | | | TB0176F | A123 | 2 | | ALL |
| 081 | 24 | | PK | | 6-8 | 24-51-61 | D04048P | 29 | | | D00278B | A11 | | | ALL |
| 082 | 24 | | PK | | 6-8 | 24-51-61 | D04048P | 30 | | | D00278B | B11 | | | ALL |
| 083 | 24 | | PK | | 5-4 | 24-51-31 | D00278A | D10 | | | TB0176F | C123 | 2 | | ALL |
| 084 | 22 | | PA | | 2-10 | 24-22-41 | D00264B | D15 | | | GDX0008 | D.. | 2 | | 050-099, 150-199, 275-276 |
| 084 | 22 | | PA | | 2-8 | 24-22-41 | D00264B | D15 | | | GDX0009 | D.. | 2 | | 277-299 |
| 085 | 22 | | PA | | 2-10 | 24-22-41 | D00264B | A08 | | | GDX0008 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 085 | 22 | | PA | | 2-8 | 24-22-41 | D00264B | A08 | | | GDX0009 | S.. | 2 | | 277-299 |
| 087 | 24 | | PK | | 6-0 | 24-22-41 | D00264A | D04 | | | D04048P | 51 | | | ALL |
| 088 | 24 | | PK | | 6-7 | 24-41-11 | D04048P | 4 | | | TB0176G | 81 | 2 | | ALL |
| 089 | 22 | | PA | | 3-8 | 25-31-21 | D00278B | B12 | | | TB0176G | 172 | 2 | | 275-278 |
| 089 | 22 | | PA | | 3-8 | 25-31-21 | D00278B | B12 | | | TB0176F | A172 | 2 | | 280-299 |
| 090 | 24 | | PK | | 4-1 | 24-28-21 | D00278B | D04 | | | TB0176G | 163 | 2 | | ALL |
| 201B | 24 | | PW | A | 4-8 | 24-22-12 | D00278A | B12 | | | TB0176F | A134 | 2 | | ALL |
| 201R | 24 | | PW | A | 0-0 | 24-22-12 | D00278A | A12 | | | TB0176F | C134 | 2 | | ALL |
| 201Z | | | | A | 0-0 | 24-22-12 | D00278A | | | FA | TB0176F | A135 | 2 | | ALL |
| 202B | 22 | | PR | B | 4-9 | 24-22-22 | D00278A | D12 | | | TB0176F | A034 | 2 | | ALL |
| 202R | 22 | | PR | B | 0-0 | 24-22-22 | D00278A | C12 | | | TB0176F | C033 | 2 | | ALL |
| 202Z | | | | B | 0-0 | 24-22-22 | D00278A | | | FA | TB0176F | C034 | 2 | | ALL |
| 203B | 22 | | PR | D | 3-7 | 24-21-41 | D04072P | 9 | | | D00264B | A01 | | | ALL |
| 203R | 22 | | PR | D | 0-0 | 24-21-41 | D04072P | 10 | | | D00264B | B01 | | | ALL |
| 203Z | | | | D | 0-0 | 24-21-41 | D04072P | 11 | | | D00264B | C01 | | | ALL |
| 204B | 24 | | PW | F | 3-6 | 24-41-11 | D00278A | B13 | | | D00264A | B12 | | | ALL |
| 204R | 24 | | PW | F | 0-0 | 24-41-11 | D00278A | A13 | | | D00264A | A12 | | | ALL |
| 204Z | | | | F | 0-0 | 24-41-11 | D00278A | | | FA | D00264A | B11 | | | ALL |
| 205B | 24 | | PW | Y | 4-11 | 31-41-35 | D05206P | 8 | | | TB0176F | A167 | 2 | | ALL |
| 205R | 24 | | PW | Y | 0-0 | 31-41-35 | D05206P | 9 | | | TB0176F | C167 | 2 | | ALL |
| 205Z | | | | Y | 0-0 | 31-41-35 | D05206P | 10 | | | GDY0010 | S.. | 2 | | 050-099, 162-199, 277-299 |
| 205Z | | | | Y | 0-0 | 31-41-35 | D05206P | 10 | | | GDY0009 | S.. | 2 | | 150-157, 275-276 |
| 301B | 18 | | PC | M | 3-9 | 24-21-41 | D04074P | 1 | | | D00264C | 2 | | | ALL |
| 301R | 18 | | PC | M | 0-0 | 24-21-41 | D04074P | 2 | | | D00264C | 3 | | | ALL |
| 301Y | 18 | | PC | M | 0-0 | 24-21-41 | D04074P | 3 | | | D00264C | 4 | | | ALL |
| 302B | 18 | | PS | N | 4-10 | 24-21-41 | D04114P | 2 | | | SM00001 | | W | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0010
Page 54
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0018 | 286T0018 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | |
| 302R | 18 | PS | N | 0-0 | 24-21-41 | D04114P | | 3 | | | | | SM00002 | | W | | ALL |
| 302Y | 18 | PS | N | 0-0 | 24-21-41 | D04114P | | 4 | | | | | SM00003 | | W | | ALL |
| 302Z | | | N | 0-0 | 24-21-41 | D04114P | | | DED | | | | SM00002 | DED | | | ALL |
| 401B | 24 | PN | C | 3-9 | 24-21-41 | D04074P | | 4 | | | | | D00264B | A13 | | | ALL |
| 401G | 24 | PN | C | 0-0 | 24-21-41 | D04074P | | 5 | | | | | D00264B | B13 | | | ALL |
| 401R | 24 | PN | C | 0-0 | 24-21-41 | D04074P | | 6 | | | | | D00264B | C13 | | | ALL |
| 401Y | 24 | PN | C | 0-0 | 24-21-41 | D04074P | | 7 | | | | | D00264B | D13 | | | ALL |
| 402B | 24 | PN | E | 6-8 | 24-41-11 | D04048P | | 36 | | | | | D00278A | D01 | | | ALL |
| 402G | 24 | PN | E | 0-0 | 24-41-11 | D04048P | | 37 | | | | | D00278A | A01 | | | ALL |
| 402R | 24 | PN | E | 0-0 | 24-41-11 | D04048P | | 38 | | | | | D00278A | B01 | | | ALL |
| 402Y | 24 | PN | E | 0-0 | 24-41-11 | D04048P | | 39 | | | | | D00278A | C01 | | | ALL |
| 403B | 24 | PN | G | 6-0 | 24-23-11 | D04048P | | 32 | | | | | D00264B | A12 | | | ALL |
| 403G | 24 | PN | G | 0-0 | 24-23-11 | D04048P | | 33 | | | | | D00264B | B12 | | | ALL |
| 403R | 24 | PN | G | 0-0 | 24-23-11 | D04048P | | 34 | | | | | D00264B | C12 | | | ALL |
| 403Y | 24 | PN | G | 0-0 | 24-23-11 | D04048P | | 35 | | | | | D00264B | D12 | | | ALL |
| 404B | 24 | PN | H | 2-11 | 24-23-12 | D04072P | | 13 | | | | | D00278A | A07 | | | ALL |
| 404G | 24 | PN | H | 0-0 | 24-23-12 | D04072P | | 14 | | | | | D00278A | B07 | | | ALL |
| 404R | 24 | PN | H | 0-0 | 24-23-12 | D04072P | | 15 | | | | | D00278A | C07 | | | ALL |
| 404Y | 24 | PN | H | 0-0 | 24-23-12 | D04072P | | 16 | | | | | D00278A | D07 | | | ALL |
| 405B | 24 | PN | I | 2-11 | 24-23-12 | D04072P | | 1 | | | | | D00278A | A06 | | | ALL |
| 405G | 24 | PN | I | 0-0 | 24-23-12 | D04072P | | 2 | | | | | D00278A | B06 | | | ALL |
| 405R | 24 | PN | I | 0-0 | 24-23-12 | D04072P | | 3 | | | | | D00278A | C06 | | | ALL |
| 405Y | 24 | PN | I | 0-0 | 24-23-12 | D04072P | | 4 | | | | | D00278A | D06 | | | ALL |
| 406B | 24 | PN | J | 2-11 | 24-23-12 | D04072P | | 5 | | | | | D00278A | C02 | | | ALL |
| 406G | 24 | PN | J | 0-0 | 24-23-12 | D04072P | | 6 | | | | | D00278A | B02 | | | ALL |
| 406R | 24 | PN | J | 0-0 | 24-23-12 | D04072P | | 7 | | | | | D00278A | A02 | | | ALL |
| 406Y | 24 | PN | J | 0-0 | 24-23-12 | D04072P | | 8 | | | | | D00278A | D02 | | | ALL |
| 407B | 24 | PN | K | 6-8 | 24-23-12 | D04048P | | 41 | | | | | D00278A | A05 | | | ALL |
| 407G | 24 | PN | K | 0-0 | 24-23-12 | D04048P | | 42 | | | | | D00278A | B05 | | | ALL |
| 407R | 24 | PN | K | 0-0 | 24-23-12 | D04048P | | 43 | | | | | D00278A | C05 | | | ALL |
| 407Y | 24 | PN | K | 0-0 | 24-23-12 | D04048P | | 44 | | | | | D00278A | D05 | | | ALL |
| FRA | | | | 0-0 | 24-22-22 | D00278A | | | | FA | | | D00278A | A14 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0010

Page 55 End

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0020 | 286T0020 | | | E6-A2-APU CONTROL | | | | | | | | | | | |
| 001 | 24 | | PK | | 7-0 | 49-14-11 | D04082P | | | | D00408B | J05 | | | ALL |
| 002 | 24 | | PK | | 7-0 | 49-14-11 | D04082P | | | | D00408B | J04 | | | ALL |
| 003 | 24 | | PK | | 7-0 | 49-14-11 | D04082P | | | | D00408B | F07 | | | ALL |
| 004 | 24 | | PK | | 7-0 | 49-14-11 | D04082P | | | | D00408B | D11 | | | ALL |
| 005 | 24 | | PK | | 7-0 | 49-14-11 | D04082P | | | | D00408B | F06 | | | ALL |
| 007 | 20 | | PA | | 6-10 | 24-32-41 | D04046P | | | | D06396P | 10 | | | 275-299 |
| 008 | 24 | | PK | | 7-0 | 49-14-11 | D04082P | | | | D00408B | J08 | | | ALL |
| 009 | 24 | | PK | | 7-0 | 49-14-11 | D04082P | | | | D00408B | C05 | | | ALL |
| 010 | 24 | | PK | | 7-0 | 49-14-11 | D04082P | | | | D00408B | J07 | | | ALL |
| 011 | 20 | | PA | | 6-11 | 49-14-11 | D04082P | | | | D00408C | 4 | | | ALL |
| 013 | 18 | | PA | | 1-7 | 33-31-31 | D04044P | | | | D04040P | 1 | DL | | ALL |
| 014 | 24 | | PK | | 6-10 | 24-51-71 | D04046P | | | | D06396P | 25 | | | ALL |
| 015 | 24 | | PK | | 6-10 | 24-51-71 | D04046P | | | | D06396P | 20 | | | ALL |
| 017 | 22 | | PA | | 7-1 | 49-15-11 | D04082P | | | | D06396P | 28 | | | ALL |
| 018 | 16 | | PA | | 7-1 | 49-15-11 | D04082P | | FM | | D06396P | 21 | | | ALL |
| 019 | 16 | | PA | | 7-1 | 49-15-11 | D04082P | | FM | | D06396P | 23 | | | ALL |
| 020 | 20 | | PA | | 7-1 | 49-15-11 | D04082P | | | | D06396P | 24 | | | ALL |
| 021 | 24 | | PK | | 7-1 | 49-15-11 | D04082P | | | | D06396P | 26 | | | ALL |
| 022 | 24 | | PK | | 6-4 | 49-15-11 | D05054P | | | | D06396P | 22 | | | ALL |
| 023 | 22 | | PA | | 6-10 | 49-61-11 | D04046P | | | | D06396P | 32 | | | ALL |
| 024 | 22 | | PA | | 6-9 | 49-61-11 | D04046P | | | | D00408B | B08 | | | ALL |
| 025 | 22 | | PA | | 6-9 | 49-61-11 | D04046P | | | | D00408B | A05 | | | ALL |
| 026 | 22 | | PA | | 6-9 | 49-61-11 | D04046P | | | | D00408B | H07 | | | ALL |
| 027 | 24 | | PK | | 6-9 | 24-22-41 | D04046P | | | | D00408B | J06 | | | ALL |
| 028 | 22 | | PA | | 6-9 | 49-61-11 | D04046P | | | | D00408B | D06 | | | ALL |
| 029 | 22 | | PA | | 6-10 | 49-61-11 | D04046P | | | | TB0026G | 3 | 2 | | ALL |
| 030 | 24 | | PK | | 1-11 | 36-11-41 | TB0026G | | 2 | | D00408B | G05 | | | 150-157 |
| 031 | 24 | | PK | | 1-11 | 36-11-41 | TB0026F | C002 | 2 | | D00408B | D03 | | | ALL |
| 032 | 24 | | PK | | 4-2 | 49-41-11 | D00408C | | | | D06396P | 29 | | | ALL |
| 033 | 22 | | PA | | 1-11 | 49-61-11 | D00408B | | H08 | | TB0026G | 3 | 2 | | ALL |
| 034 | 16 | | PA | | 4-2 | 49-61-11 | D00408C | | | | D06396P | 30 | FM | | ALL |
| 035 | 16 | | PA | | 1-9 | 49-61-11 | D00408C | | | | GDX0002 | D.. | 2 | | ALL |
| 036 | 16 | | PA | | 1-9 | 49-61-11 | D00408C | | | | GDX0002 | S.. | 2 | | ALL |
| 037 | 16 | | PA | | 6-4 | 49-61-11 | D05054P | | | | D06396P | 33 | FM | | ALL |
| 038 | 24 | | PK | | 6-3 | 73-21-15 | D00408B | | D05 | | D05054P | 11 | | | ALL |
| 039 | 24 | | PK | | 6-9 | 29-11-32 | D00408B | | D04 | | D04046P | 20 | | | ALL |
| 044 | 24 | | PK | | 6-5 | 24-31-41 | D05054P | | | | TB0026G | 1 | 2 | | ALL |
| 049 | 24 | | PK | | 7-1 | 49-15-11 | D06396P | | | | D04082P | 46 | | | ALL |
| 050 | 24 | | PK | | 4-4 | 49-15-11 | D06396P | | | | D00408B | B07 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 1

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--------------------------------------|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0020 | 286T0020 | | | E6-A2-APU CONTROL (continued) | | | | | | | | | | | | | |
| 052 | 22 | | PA | | 4-6 | 49-61-11 | D06396P | | 31 | | | | TB0026G | 3 | 2 | | ALL |
| 054 | 24 | | PK | | 7-2 | 36-11-41 | D04082P | | 7 | | | | TB0026F | A004 | 2 | | ALL |
| 055 | 20 | | PA | | 7-2 | 36-11-41 | D04082P | | 11 | | | | TB0026F | C004 | 2 | | ALL |
| 056 | 20 | | PA | | 7-2 | 36-11-41 | D04082P | | 12 | | | | TB0026F | A005 | 2 | | ALL |
| 057 | 24 | | PK | | 7-2 | 36-11-41 | D04082P | | 8 | | | | TB0026F | C005 | 2 | | ALL |
| 058 | 20 | | PA | | 6-11 | 49-14-11 | D04082P | | 34 | | | | D00408C | 6 | | | ALL |
| 059 | 24 | | PK | | 7-0 | 49-14-11 | D04082P | | 23 | | | | D00408B | B10 | | | ALL |
| 061 | 24 | | PK | | 7-0 | 49-14-11 | D04082P | | 31 | | | | D00408B | J10 | | | ALL |
| 063 | 22 | | PA | | 1-11 | 49-61-11 | D00408B | | F03 | | | | GDX0002 | D.. | 2 | | ALL |
| 064 | 24 | | PK | | 6-4 | 31-31-22 | D06396P | | 1 | | | | D05054P | 1 | | | ALL |
| 065 | 22 | | PA | | 6-3 | 49-61-11 | D00408B | | K06 | | | | D05054P | 3 | | | ALL |
| 066 | 22 | | PA | | 6-3 | 80-11-11 | D05054P | | 9 | | | | D00408B | D07 | | | ALL |
| 068 | 24 | | PK | | 6-9 | 49-71-11 | D00408B | | K04 | | | | D04046P | 10 | | | ALL |
| 070 | 24 | | PK | | 6-8 | 24-27-41 | TB0026D | | A032 | 2 | | | D04044P | 12 | | | 150-157 |
| 071 | 24 | | PK | | 2-8 | 24-27-41 | TB0026D | | C032 | 2 | | | TB0026G | 6 | 2 | | 150-157 |
| 072 | 24 | | PK | | 6-9 | 49-73-11 | D04046P | | 26 | | | | D00408B | K07 | | | ALL |
| 073 | 24 | | PK | | 6-10 | 24-34-11 | D06396P | | 17 | | | | D04046P | 23 | | | ALL |
| 074 | 22 | | PA | | 6-9 | 49-61-11 | D04046P | | 25 | | | | D00408B | G05 | | | 050-099, 162-199, 275-299 |
| 086 | 24 | | PK | | 6-10 | 38-15-11 | D04046P | | 18 | | | | D06396P | 34 | | | ALL |
| 087 | 22 | | PA | | 7-1 | 49-15-11 | D06396P | | 8 | | | | D04082P | 24 | | | ALL |
| 129 | 24 | | PK | | 6-4 | 31-31-22 | D06396P | | 3 | | | | D05054P | 10 | | | ALL |
| 130 | 24 | | PK | | 6-4 | 31-31-22 | D06396P | | 2 | | | | D05054P | 12 | | | ALL |
| 201B | 24 | | PW | D | 7-0 | 49-14-11 | D04082P | | 13 | | | | D00408B | H11 | | | ALL |
| 201R | 24 | | PW | D | 0-0 | 49-14-11 | D04082P | | 14 | | | | D00408B | H10 | | | ALL |
| 201Z | | | | D | 0-0 | 49-14-11 | D04082P | | | | FC | | D00408B | | | FA | ALL |
| 202B | 24 | | PW | E | 7-0 | 49-14-11 | D04082P | | 15 | | | | D00408B | G09 | | | ALL |
| 202R | 24 | | PW | E | 0-0 | 49-14-11 | D04082P | | 16 | | | | D00408B | G08 | | | ALL |
| 202Z | | | | E | 0-0 | 49-14-11 | D04082P | | | | FC | | D00408B | | | FA | ALL |
| 203B | 24 | | PW | F | 7-0 | 49-14-11 | D04082P | | 17 | | | | D00408B | G07 | | | ALL |
| 203R | 24 | | PW | F | 0-0 | 49-14-11 | D04082P | | 18 | | | | D00408B | G06 | | | ALL |
| 203Z | | | | F | 0-0 | 49-14-11 | D04082P | | | | FC | | D00408B | | | FA | ALL |
| 204B | 24 | | PW | G | 7-0 | 49-14-11 | D04082P | | 19 | | | | D00408B | B06 | | | ALL |
| 204R | 24 | | PW | G | 0-0 | 49-14-11 | D04082P | | 20 | | | | D00408B | B05 | | | ALL |
| 204Z | | | | G | 0-0 | 49-14-11 | D04082P | | | | FB | | D00408B | | | FA | ALL |
| 205B | 24 | | PW | H | 7-0 | 49-14-11 | D04082P | | 21 | | | | D00408B | A11 | | | ALL |
| 205R | 24 | | PW | H | 0-0 | 49-14-11 | D04082P | | 22 | | | | D00408B | A10 | | | ALL |
| 205Z | | | | H | 0-0 | 49-14-11 | D04082P | | | | FB | | D00408B | | | FA | ALL |
| 206B | 20 | | PR | M | 1-7 | 24-21-41 | D04044P | | 1 | | | | D04040P | 5 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 2

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0020 | 286T0020 | | | E6-A2-APU CONTROL (continued) | | | | | | | | | | | |
| 206R | 20 | PR | M | 0-0 | 24-21-41 | D04044P | | 2 | | | D04040P | 6 | | | ALL |
| 206Z | | | M | 0-0 | 24-21-41 | D04044P | | 3 | | | D04040P | 7 | | | ALL |
| 208B | 22 | PB | Q | 6-9 | 21-61-51 | D04046P | | 15 | | | D00408B | D08 | | | ALL |
| 208R | 22 | PB | Q | 0-0 | 21-61-51 | D04046P | | 16 | | | D00408B | D09 | | | ALL |
| 209B | 22 | PR | R | 7-0 | 49-14-11 | D04082P | | 1 | | | D00408B | A04 | | | ALL |
| 209R | 22 | PR | R | 0-0 | 49-14-11 | D04082P | | 2 | | | D00408B | A03 | | | ALL |
| 209Z | | | R | 0-0 | 49-14-11 | D04082P | | | | FC | D00408B | | | FA | ALL |
| 210B | 24 | PW | A | 7-0 | 49-14-11 | D04082P | | 3 | | | D00408B | A02 | | | ALL |
| 210R | 24 | PW | A | 0-0 | 49-14-11 | D04082P | | 4 | | | D00408B | A01 | | | ALL |
| 210Z | | | A | 0-0 | 49-14-11 | D04082P | | | | FC | D00408B | | | FA | ALL |
| 211B | 24 | PW | B | 7-0 | 49-14-11 | D04082P | | 5 | | | D00408B | B04 | | | ALL |
| 211R | 24 | PW | B | 0-0 | 49-14-11 | D04082P | | 6 | | | D00408B | B03 | | | ALL |
| 211Z | | | B | 0-0 | 49-14-11 | D04082P | | | | FC | D00408B | | | FA | ALL |
| 212B | 24 | PW | C | 7-0 | 49-14-11 | D04082P | | 9 | | | D00408B | C09 | | | ALL |
| 212R | 24 | PW | C | 0-0 | 49-14-11 | D04082P | | 10 | | | D00408B | C08 | | | ALL |
| 212Z | | | C | 0-0 | 49-14-11 | D04082P | | | | FC | D00408B | | | FA | ALL |
| 213B | 24 | PW | S | 7-0 | 49-14-11 | D04082P | | 40 | | | D00408B | E05 | | | ALL |
| 213R | 24 | PW | S | 0-0 | 49-14-11 | D04082P | | 41 | | | D00408B | E04 | | | ALL |
| 213Z | | | S | 0-0 | 49-14-11 | D04082P | | DED | | | D00408B | | | FA | ALL |
| 214B | 24 | PW | T | 7-0 | 49-14-11 | D04082P | | 52 | | | D00408B | F11 | | | ALL |
| 214R | 24 | PW | T | 0-0 | 49-14-11 | D04082P | | 53 | | | D00408B | F08 | | | ALL |
| 214Z | | | T | 0-0 | 49-14-11 | D04082P | | | | FC | D00408B | | | FA | ALL |
| 215B | 24 | PW | U | 7-0 | 49-14-11 | D04082P | | 54 | | | D00408B | F09 | | | ALL |
| 215R | 24 | PW | U | 0-0 | 49-14-11 | D04082P | | 55 | | | D00408B | F10 | | | ALL |
| 215Z | | | U | 0-0 | 49-14-11 | D04082P | | | | FC | D00408B | | | FA | ALL |
| 217B | 24 | PL | V | 6-10 | 24-34-11 | D04046P | | 28 | | | D06396P | 15 | | | ALL |
| 217R | 24 | PL | V | 0-0 | 24-34-11 | D04046P | | 29 | | | D06396P | 16 | | | ALL |
| 301B | 18 | PC | N | 1-7 | 24-21-41 | D04044P | | 4 | | | D04040P | 2 | DL | | ALL |
| 301R | 18 | PC | N | 0-0 | 24-21-41 | D04044P | | 5 | | | D04040P | 3 | DL | | ALL |
| 301Y | 18 | PC | N | 0-0 | 24-21-41 | D04044P | | 6 | | | D04040P | 4 | DL | | ALL |
| 302B | 24 | PM | I | 1-9 | 49-94-14 | D05054P | | 6 | | | D06424P | 2 | | | ALL |
| 302R | 24 | PM | I | 0-0 | 49-94-14 | D05054P | | 5 | | | D06424P | 1 | | | ALL |
| 302Y | 24 | PM | I | 0-0 | 49-94-14 | D05054P | | 7 | | | D06424P | 3 | | | ALL |
| 404B | 24 | PN | O | 1-7 | 24-21-41 | D04044P | | 7 | | | D04040P | 8 | | | ALL |
| 404G | 24 | PN | O | 0-0 | 24-21-41 | D04044P | | 8 | | | D04040P | 9 | | | ALL |
| 404R | 24 | PN | O | 0-0 | 24-21-41 | D04044P | | 9 | | | D04040P | 10 | | | ALL |
| 404Y | 24 | PN | O | 0-0 | 24-21-41 | D04044P | | 10 | | | D04040P | 11 | | | ALL |
| 452G | 22 | DU | J | 7-0 | 49-14-11 | D04082P | | 27 | 4F | | D00408B | E06 | 63 | | 050, 155-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0020
Page 3
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0020 | 286T0020 | | | E6-A2-APU CONTROL (continued) | | | | | | | | | | | | |
| 452G | 22 | DU | J | 7-0 | 49-14-11 | D04082P | 27 | 4F | | D00408B | E06 | | | 051-099, 150-154, 275-276 | | |
| 452W | 22 | DU | J | 0-0 | 49-14-11 | D04082P | 26 | 4J | | D00408B | E07 | 62 | | 050, 155-199, 277-299 | | |
| 452W | 22 | DU | J | 0-0 | 49-14-11 | D04082P | 26 | 4J | | D00408B | E07 | | | 051-099, 150-154, 275-276 | | |
| 452Z | | | J | 0-0 | 49-14-11 | D04082P | | | FB | D00408B | | | FA | ALL | | |
| 453G | 22 | DU | K | 7-0 | 49-14-11 | D04082P | 30 | 4F | | D00408B | A08 | 63 | | 050, 155-199, 277-299 | | |
| 453G | 22 | DU | K | 7-0 | 49-14-11 | D04082P | 30 | 4F | | D00408B | A08 | | | 051-099, 150-154, 275-276 | | |
| 453W | 22 | DU | K | 0-0 | 49-14-11 | D04082P | 29 | 4J | | D00408B | A09 | 62 | | 050, 155-199, 277-299 | | |
| 453W | 22 | DU | K | 0-0 | 49-14-11 | D04082P | 29 | 4J | | D00408B | A09 | | | 051-099, 150-154, 275-276 | | |
| 453Z | | | K | 0-0 | 49-14-11 | D04082P | | | FB | D00408B | | | FA | ALL | | |
| 454G | 22 | DU | L | 7-0 | 49-14-11 | D04082P | 33 | 4F | | D00408B | A06 | 63 | | 050, 155-199, 277-299 | | |
| 454G | 22 | DU | L | 7-0 | 49-14-11 | D04082P | 33 | 4F | | D00408B | A06 | | | 051-099, 150-154, 275-276 | | |
| 454W | 22 | DU | L | 0-0 | 49-14-11 | D04082P | 32 | 4J | | D00408B | A07 | 62 | | 050, 155-199, 277-299 | | |
| 454W | 22 | DU | L | 0-0 | 49-14-11 | D04082P | 32 | 4J | | D00408B | A07 | | | 051-099, 150-154, 275-276 | | |
| 454Z | | | L | 0-0 | 49-14-11 | D04082P | | | FB | D00408B | | | FA | ALL | | |
| FRA | | | | 0-0 | 49-14-11 | D00408B | | | FA | D00408B | J09 | | | ALL | | |
| FRB | | | | 0-0 | 49-14-11 | D04082P | 28 | | | D04082P | | | FB | ALL | | |
| FRC | | | | 0-0 | 49-14-11 | D04082P | | | FC | D04082P | 25 | | | ALL | | |
| W0022 | 286T0022 | | | P31-L2-L.GEN PWR DISTRIBUTION CONTROL | | | | | | | | | | | | |
| 001 | 24 | PK | | 3-6 | 24-22-12 | D04054J | 5 | | | D00254 | 3 | | | ALL | | |
| 002 | 18 | PA | | 4-10 | 24-22-11 | D04080J | 4 | DK | | C00901 | L2 | H | | ALL | | |
| 003 | 24 | PK | | 5-3 | 24-22-11 | D04054J | 4 | | | D00252 | 3 | | | ALL | | |
| 004 | 20 | PA | | 5-3 | 24-22-11 | D04054J | 23 | | | D00252 | 39 | | | ALL | | |
| 005 | 20 | PA | | 3-3 | 24-22-11 | D04054J | 22 | | | TB0028D | A006 | 2 | | ALL | | |
| 006 | 20 | PA | | 4-2 | 24-22-11 | GDX0001 | D.. | 2 | | D00252 | 40 | | | ALL | | |
| 007 | 20 | PA | | 4-3 | 24-22-11 | TB0028D | C006 | 2 | | D00252 | 37 | | | ALL | | |
| 008 | 20 | PA | | 5-3 | 24-22-11 | D04054J | 21 | | | D00252 | 41 | | | ALL | | |
| 009 | 20 | PA | | 3-5 | 24-51-13 | GDX0001 | D.. | 2 | | K00119 | 13 | C | | ALL | | |
| 010 | 24 | PK | | 2-4 | 24-51-13 | D04054J | 3 | | | K00119 | X1 | C | | ALL | | |
| 011 | 24 | PK | | 2-4 | 24-51-13 | D04054J | 19 | | | K00119 | X2 | C | | ALL | | |
| 012 | 24 | PK | | 2-0 | 24-51-13 | D04054J | 20 | | | K00119 | 14 | C | | ALL | | |
| 013 | 24 | PK | | 3-3 | 24-27-11 | D04080J | 29 | | | D00254 | 16 | | | ALL | | |
| 014 | 20 | PA | | 2-5 | 24-27-11 | GDX0001 | D.. | 2 | | D00254 | 2 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 4

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0022 | 286T0022 | | | P31-L2-L.GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | |
| 015 | 20 | | PA | 2-5 | 24-22-12 | GDX0001 | D.. | 2 | | D00254 | | 10 | | ALL | |
| 016 | 24 | | PK | 3-6 | 24-22-12 | D04054J | | 54 | | D00254 | | 9 | | ALL | |
| 017 | 24 | | PK | 2-5 | 24-27-11 | TB0028G | | 2 | 2 | D00254 | | 1 | | ALL | |
| 018 | 24 | | PK | 2-5 | 24-27-11 | TB0028G | | 2 | 2 | D00254 | | 15 | | ALL | |
| 019 | 24 | | PK | 4-2 | 24-27-11 | TB0028G | | 2 | 2 | D00252 | | 2 | | ALL | |
| 020 | 20 | | PA | 4-2 | 24-27-11 | GDX0001 | D.. | 2 | | D00252 | | 10 | | ALL | |
| 021 | 24 | | PK | 3-0 | 24-27-11 | D04080J | | 16 | | TB0030Y | A012 | BJ | | 050-099 | |
| 021 | 24 | | PK | 3-0 | 24-27-11 | D04080J | | 16 | | TB0030G | 12 | 2 | | 150-199, 275-299 | |
| 022 | 24 | | PK | 2-11 | 24-27-11 | D04080J | | 17 | | TB0030G | 2 | 2 | | ALL | |
| 023 | 24 | | PK | 3-2 | 24-27-21 | D04054J | | 27 | | TB0028G | 3 | 2 | | ALL | |
| 024 | 24 | | PK | 3-2 | 24-27-21 | D04054J | | 28 | | TB0028G | 4 | 2 | | ALL | |
| 025 | 24 | | PK | 2-5 | 24-27-21 | TB0028G | | 3 | 2 | D00254 | | 22 | | ALL | |
| 026 | 24 | | PK | 2-5 | 24-27-21 | TB0028G | | 3 | 2 | D00254 | | 24 | | ALL | |
| 027 | 24 | | PK | 2-5 | 24-27-21 | TB0028G | | 4 | 2 | D00254 | | 21 | | ALL | |
| 028 | 24 | | PK | 4-0 | 24-27-21 | D00252 | | 6 | | D00254 | | 23 | | ALL | |
| 029 | 24 | | PK | 4-2 | 24-27-21 | TB0028G | | 4 | 2 | D00252 | | 5 | | ALL | |
| 030 | 24 | | PK | 8-0 | 24-28-11 | D04054J | | 18 | | C00818 | 2 | D | | ALL | |
| 031 | 18 | | PA | 10-5 | 24-28-11 | C00818 | | 1 | D | C00901 | T2 | H | | ALL | |
| 032 | 24 | | PK | 4-4 | 25-31-21 | D00390 | | 1 | | D04068J | 8 | | | ALL | |
| 033 | 24 | | PK | 4-4 | 25-31-21 | D00390 | | 2 | | D04068J | 5 | | | ALL | |
| 034 | 24 | | PK | 4-4 | 25-31-21 | D00390 | | 3 | | D04068J | 6 | | | ALL | |
| 035 | 24 | | PK | 4-4 | 25-31-21 | D00390 | | 4 | | D04068J | 9 | | | ALL | |
| 036 | 22 | | PA | 1-0 | 25-31-21 | D00390 | | 11 | | D00390 | 14 | | | 050-099, 150-199 | |
| 036 | 22 | | PA | 1-0 | 25-31-21 | D00390 | | 11 | | D00390 | 13 | | | 275-299 | |
| 038 | 24 | | PK | 5-0 | 24-51-71 | D04080J | | 20 | | D00252 | 25 | | | ALL | |
| 039 | 16 | | PA | 2-11 | 25-31-21 | D04080J | | 23 | | SM00001 | | W | | 275-276 | |
| 039 | 16 | | PA | 1-9 | 25-31-21 | D04080J | | 23 | | D04068J | 10 | | | 277-299 | |
| 040 | 20 | | PA | 4-3 | 25-31-21 | D04080J | | 21 | | D00390 | 8 | | | 050-099 | |
| 040 | 20 | | PA | 6-0 | 25-31-21 | D00390 | | 8 | | TB0028G | 1 | 2 | | 150-199 | |
| 040 | 18 | | PA | 6-0 | 25-31-21 | D00390 | | 8 | DK | TB0028G | 1 | 2 | | 275-278 | |
| 041 | 24 | | PK | 4-10 | 24-51-71 | D04052J | | 10 | | D00252 | 26 | | | ALL | |
| 042 | 20 | | PA | 2-11 | 25-31-21 | TB0028G | | 1 | 2 | D04080J | 21 | | | 150-199 | |
| 042 | 18 | | PA | 2-11 | 25-31-21 | TB0028G | | 1 | 2 | D04080J | 21 | | | 275-278 | |
| 042 | 18 | | PA | 4-3 | 25-31-21 | D00390 | | 8 | DK | D04080J | 21 | | | 280-299 | |
| 044 | 22 | | PA | 4-3 | 25-31-21 | D04080J | | 9 | | D00390 | 9 | | | 050-099 | |
| 044 | 22 | | PA | 3-2 | 25-31-21 | D04080J | | 9 | | TB0028Y | C013 | BJ | | 150-199, 275-299 | |
| 047 | 24 | | PK | 5-3 | 24-22-12 | D00252 | | 7 | | D04054J | 1 | | | ALL | |
| 048 | 18 | | PA | 3-3 | 24-22-12 | C00902 | | L2 | H | D04080J | 5 | DK | | ALL | |
| 049 | 24 | | PK | 3-6 | 24-22-12 | D00254 | | 7 | | D04054J | 2 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 5

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0022 | 286T0022 | | | P31-L2-L.GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | | |
| 050 | 20 | | PA | 2-6 | 24-22-12 | D00254 | | 37 | | | | | TB0028D | C007 | 2 | | ALL |
| 051 | 20 | | PA | 3-3 | 24-22-12 | TB0028D | | A007 | 2 | | | | D04054J | 24 | | | ALL |
| 052 | 20 | | PA | 2-5 | 24-22-12 | D00254 | | 40 | | | | | GDX0001 | D.. | 2 | | ALL |
| 053 | 20 | | PA | 3-6 | 24-22-12 | D00254 | | 41 | | | | | D04054J | 25 | | | ALL |
| 054 | 20 | | PA | 2-6 | 24-22-12 | D00254 | | 39 | | | | | TB0030G | 8 | 2 | | ALL |
| 055 | 20 | | PA | 2-5 | 24-22-12 | GDX0001 | | D.. | 2 | | | | D00254 | 4 | | | ALL |
| 056 | 20 | | PA | 4-2 | 24-22-11 | GDX0001 | | D.. | 2 | | | | D00252 | 4 | | | ALL |
| 057 | 20 | | PA | 4-2 | 24-22-12 | GDX0001 | | D.. | 2 | | | | D00252 | 8 | | | ALL |
| 058 | 20 | | PA | 2-5 | 24-22-12 | GDX0001 | | D.. | 2 | | | | D00254 | 8 | | | ALL |
| 060 | 18 | | PA | 3-1 | 24-21-11 | D04080J | | 1 | DK | | | | TB0028F | A009 | 2 | | ALL |
| 061 | 18 | | PA | 3-1 | 24-21-11 | D04080J | | 2 | DK | | | | TB0028F | C009 | 2 | | ALL |
| 062 | 18 | | PA | 3-1 | 24-21-11 | D04080J | | 3 | DK | | | | TB0028F | A010 | 2 | | ALL |
| 063 | 22 | | PA | 0-7 | 29-11-31 | D03450 | | 11 | | | | | D03450 | 12 | | | ALL |
| 064 | 22 | | PA | 6-6 | 29-11-31 | D03450 | | 1 | | | | | TB0030Y | C003 | BJ | | ALL |
| 065 | 22 | | PA | 6-6 | 29-11-31 | D03450 | | 2 | | | | | TB0030Y | C003 | BJ | | ALL |
| 066 | 22 | | PA | 6-6 | 29-11-31 | D03450 | | 3 | | | | | TB0030Y | C003 | BJ | | ALL |
| 067 | 24 | | PK | 6-7 | 29-11-31 | D03450 | | 10 | | | | | TB0030Y | C005 | BJ | | ALL |
| 068 | 22 | | PA | 6-1 | 29-11-31 | D03450 | | 8 | | | | | M00303 | B | C | | ALL |
| 071 | 24 | | PK | 1-0 | 29-11-22 | D03448 | | 11 | | | | | D03448 | 12 | | | ALL |
| 072 | 24 | | PK | 4-9 | 29-11-22 | TB0030Y | | A004 | BJ | | | | D03448 | 1 | | | ALL |
| 073 | 24 | | PK | 4-9 | 29-11-22 | TB0030Y | | A004 | BJ | | | | D03448 | 2 | | | ALL |
| 074 | 24 | | PK | 4-9 | 29-11-22 | TB0030Y | | A004 | BJ | | | | D03448 | 3 | | | ALL |
| 075 | 24 | | PK | 4-9 | 29-11-22 | D03448 | | 10 | | | | | TB0030Y | A005 | BJ | | ALL |
| 076 | 24 | | PK | 4-9 | 29-11-22 | D03448 | | 8 | | | | | TB0030Y | A006 | BJ | | ALL |
| 077 | 22 | | PA | 3-2 | 29-32-11 | D04054J | | 38 | | | | | TB0030F | A001 | 2 | | ALL |
| 083 | 24 | | PK | 4-9 | 29-11-22 | D03448 | | 9 | | | | | TB0030Y | A005 | BJ | | ALL |
| 084 | 20 | | PA | 4-0 | 29-11-22 | D03448 | | 15 | | | | | GDX0002 | A.. | 2 | | ALL |
| 085 | 24 | | PK | 6-7 | 29-11-31 | D03450 | | 9 | | | | | TB0030Y | C005 | BJ | | ALL |
| 086 | 24 | | PK | 5-3 | 24-22-11 | D04054J | | 40 | | | | | D00252 | 21 | | | ALL |
| 087 | 20 | | PA | 4-3 | 24-22-12 | TB0030G | | 8 | 2 | | | | D00252 | 14 | | | ALL |
| 088 | 20 | | PA | 3-3 | 24-22-12 | TB0030G | | 8 | 2 | | | | D04054J | 46 | | | ALL |
| 089 | 24 | | PK | 2-6 | 24-51-31 | TB0030Y | | C006 | BJ | | | | D00254 | 25 | | | ALL |
| 090 | 24 | | PK | 4-3 | 24-51-31 | TB0030Y | | C006 | BJ | | | | D00252 | 28 | | | ALL |
| 091 | 24 | | PK | 3-3 | 24-51-31 | TB0030Y | | C006 | BJ | | | | D04054J | 45 | | | ALL |
| 092 | 24 | | PK | 4-3 | 24-51-31 | TB0030Y | | A011 | BJ | | | | D00252 | 27 | | | 050-099 |
| 092 | 24 | | PK | 4-3 | 24-51-31 | TB0030G | | 10 | 2 | | | | D00252 | 27 | | | 150-199, 275-299 |
| 093 | 24 | | PK | 3-3 | 24-51-31 | TB0030Y | | A011 | BJ | | | | D04054J | 43 | | | 050-099 |
| 093 | 24 | | PK | 3-3 | 24-51-31 | TB0030G | | 10 | 2 | | | | D04054J | 43 | | | 150-199, 275-299 |
| 094 | 24 | | PK | 3-11 | 24-51-31 | TB0030Y | | A011 | BJ | | | | D00422 | B2 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 6

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0022 | 286T0022 | | | P31-L2-L.GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | |
| 094 | 24 | | PK | 3-11 | 24-51-31 | TB0030G | 10 | 2 | | D00422 | | B2 | | 150-199, 275-299 | |
| 095 | 24 | | PK | 3-11 | 24-51-31 | TB0030Y | A011 | BJ | | D00422 | | X1 | | 050-099 | |
| 095 | 24 | | PK | 3-11 | 24-51-31 | TB0030G | 10 | 2 | | D00422 | | X1 | | 150-199, 275-299 | |
| 096 | 20 | | PA | 3-10 | 24-51-31 | GDX0001 | D.. | 2 | | D00422 | | X2 | | ALL | |
| 097 | 20 | | PA | 2-4 | 24-22-12 | D04054J | 26 | | | D00422 | | A3 | | ALL | |
| 098 | 20 | | PA | 3-11 | 24-22-12 | TB0030Y | C011 | BJ | | D00422 | | A2 | | 050-099 | |
| 098 | 20 | | PA | 3-11 | 24-22-12 | TB0030G | 11 | 2 | | D00422 | | A2 | | 150-199, 275-299 | |
| 099 | 20 | | PA | 3-3 | 24-22-12 | TB0030Y | C011 | BJ | | D04054J | | 42 | | 050-099 | |
| 099 | 20 | | PA | 3-3 | 24-22-12 | TB0030G | 11 | 2 | | D04054J | | 42 | | 150-199, 275-299 | |
| 100 | 20 | | PA | 4-3 | 24-22-12 | TB0030Y | C011 | BJ | | D00252 | | 13 | | 050-099 | |
| 100 | 20 | | PA | 4-3 | 24-22-12 | TB0030G | 11 | 2 | | D00252 | | 13 | | 150-199, 275-299 | |
| 101 | 24 | | PK | 5-3 | 24-22-12 | D04054J | 44 | | | D00252 | | 22 | | ALL | |
| 102 | 24 | | PK | 3-6 | 24-51-31 | D04054J | 41 | | | D00254 | | 27 | | ALL | |
| 103 | 24 | | PK | 3-6 | 24-51-31 | D04054J | 47 | | | D00254 | | 28 | | ALL | |
| 104 | 20 | | PA | 5-3 | 24-22-22 | D04054J | 49 | | | D00252 | | 17 | | ALL | |
| 105 | 20 | | PA | 5-3 | 24-22-22 | D04054J | 48 | | | D00252 | | 18 | | ALL | |
| 106 | 22 | | PA | 2-9 | 29-11-31 | D04054J | 34 | | | M00303 | | A | C | *1 ALL | |
| 107 | 24 | | PK | 3-2 | 29-11-31 | D04054J | 52 | | | TB0030Y | C004 | BJ | | ALL | |
| 108 | 22 | | PA | 3-2 | 29-11-31 | D04054J | 37 | | | TB0030Y | A003 | BJ | | ALL | |
| 109 | 24 | | PK | 3-2 | 29-11-31 | D04054J | 51 | | | TB0030Y | A003 | BJ | | ALL | |
| 110 | 24 | | PK | 3-3 | 29-11-31 | D04054J | 50 | | | TB0030G | 7 | 2 | | ALL | |
| 111 | 24 | | PK | 2-5 | 29-11-31 | D00254 | 17 | | | TB0030Y | A003 | BJ | | ALL | |
| 112 | 24 | | PK | 2-6 | 29-11-31 | D00254 | 18 | | | TB0030G | 7 | 2 | | ALL | |
| 113 | 24 | | PK | 2-5 | 29-11-31 | D00254 | 19 | | | TB0030Y | A003 | BJ | | ALL | |
| 114 | 24 | | PK | 2-5 | 29-11-31 | D00254 | 20 | | | TB0030Y | C004 | BJ | | ALL | |
| 115 | 24 | | PK | 6-7 | 29-11-31 | D03450 | 5 | | | TB0030G | 7 | 2 | | ALL | |
| 116 | 24 | | PK | 6-6 | 29-11-31 | D03450 | 6 | | | TB0030Y | C004 | BJ | | ALL | |
| 117 | 24 | | PK | 4-9 | 29-11-31 | D03448 | 5 | | | TB0030G | 7 | 2 | | ALL | |
| 118 | 24 | | PK | 4-9 | 29-11-31 | D03448 | 6 | | | TB0030Y | C004 | BJ | | ALL | |
| 119 | 20 | | PA | 6-1 | 25-31-21 | D00390 | 10 | | | GDX0001 | D.. | 2 | | ALL | |
| 120 | 20 | | PA | 6-1 | 25-31-21 | D00390 | 15 | | | GDX0001 | S.. | 2 | | ALL | |
| 122 | 24 | | PK | 3-3 | 24-51-31 | D00254 | 26 | | | D04080J | 12 | | | ALL | |
| 123 | 24 | | PK | 3-10 | 24-51-31 | D00422 | B1 | | | TB0028D | A008 | 2 | | ALL | |
| 124 | 24 | | PK | 2-11 | 24-51-31 | D04080J | 13 | | | TB0028D | C008 | 2 | | ALL | |
| 126 | 22 | | PA | 0-7 | 25-31-21 | D00390 | 16 | | | D00390 | 17 | | | ALL | |
| 127 | 20 | | PA | 5-3 | 29-11-31 | D03450 | 15 | | | GDX0002 | A.. | 2 | | ALL | |
| 128 | 24 | | PK | 3-3 | 29-11-22 | D04054J | 32 | | | TB0030Y | A006 | BJ | | ALL | |
| 129 | 24 | | PK | 3-0 | 31-31-26 | TB0030Y | A006 | BJ | | D04080J | 18 | | | ALL | |
| 130 | 24 | | PK | 3-1 | 24-51-71 | D04080J | 24 | | | TB0028G | 11 | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 7

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0022 | 286T0022 | | | P31-L2-L.GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | | |
| 131 | 24 | | PK | 2-11 | 24-51-71 | D04052J | | 8 | | | | | TB0028G | 12 | 2 | | ALL |
| 132 | 24 | | PK | 2-11 | 24-51-71 | D04052J | | 6 | | | | | TB0028G | 12 | 2 | | ALL |
| 133 | 24 | | PK | 2-7 | 24-51-71 | D00254 | | 6 | | | | | TB0028G | 12 | 2 | | ALL |
| 134 | 24 | | PK | 2-7 | 24-51-71 | D00254 | | 5 | | | | | TB0028G | 11 | 2 | | ALL |
| 135 | 24 | | PK | 2-11 | 24-51-71 | D04052J | | 5 | | | | | TB0028G | 11 | 2 | | ALL |
| 136 | 24 | | PK | 2-11 | 24-27-11 | D04080J | | 26 | | | | | TB0030G | 2 | 2 | | ALL |
| 137 | 24 | | PK | 4-2 | 24-27-11 | D00252 | | 1 | | | | | TB0030G | 2 | 2 | | ALL |
| 138 | 24 | | PK | 3-0 | 24-27-11 | D04080J | | 25 | | | | | TB0030Y | A012 | BJ | | 050-099 |
| 138 | 24 | | PK | 3-0 | 24-27-11 | D04080J | | 25 | | | | | TB0030G | 12 | 2 | | 150-199, 275-299 |
| 139 | 24 | | PK | 4-3 | 24-27-11 | D00252 | | 9 | | | | | TB0030Y | A012 | BJ | | 050-099 |
| 139 | 24 | | PK | 4-3 | 24-27-11 | D00252 | | 9 | | | | | TB0030G | 12 | 2 | | 150-199, 275-299 |
| 140 | 20 | | PA | 1-9 | 29-11-31 | GDX0002 | | | D.. | 2 | | | M00303 | G | C | | ALL |
| 143 | 24 | | PK | 2-6 | 31-31-26 | M00303 | | | B | C | | | D04080J | 19 | | | ALL |
| 144 | 18 | | PA | 1-10 | 30-71-25 | D04052J | | 7 | | DK | | | D04068J | 4 | | | 050-099, 150-199 |
| 145 | 24 | | PK | 3-3 | 29-11-22 | D04054J | | 14 | | | | | TB0030Y | A005 | BJ | | ALL |
| 146 | 24 | | PK | 3-2 | 29-11-22 | D04054J | | 16 | | | | | D03448 | 18 | | | ALL |
| 147 | 24 | | PK | 3-0 | 29-11-31 | D04080J | | 14 | | | | | TB0030Y | C005 | BJ | | ALL |
| 148 | 22 | | PA | 6-1 | 29-11-31 | D03450 | | 18 | | | | | M00303 | A | C | *1 | ALL |
| 151 | 18 | | PA | 4-6 | 25-31-31 | D00392 | | 8 | | DK | | | D04080J | 32 | DK | | 277-299 |
| 153 | 18 | | PA | 3-8 | 25-31-31 | TB0028G | | 1 | | 2 | | | D00392 | 8 | DK | | 275-276 |
| 154 | 20 | | PA | 3-8 | 25-31-31 | GDX0001 | | | D.. | 2 | | | D00392 | 10 | | | 275-299 |
| 155 | 20 | | PA | 3-8 | 25-31-31 | GDX0001 | | | S.. | 2 | | | D00392 | 15 | | | 275-299 |
| 156 | 22 | | PA | 1-0 | 25-31-31 | D00392 | | 16 | | | | | D00392 | 17 | | | 275-299 |
| 157 | 24 | | PK | 4-10 | 25-31-31 | D06380J | | 1 | | | | | D00392 | 1 | | | 275-278 |
| 157 | 24 | | PK | 4-10 | 25-31-31 | D06380J | | 8 | | | | | D00392 | 1 | | | 280-299 |
| 158 | 24 | | PK | 4-10 | 25-31-31 | D06380J | | 2 | | | | | D00392 | 2 | | | 275-278 |
| 158 | 24 | | PK | 4-10 | 25-31-31 | D06380J | | 5 | | | | | D00392 | 2 | | | 280-299 |
| 159 | 24 | | PK | 4-10 | 25-31-31 | D06380J | | 3 | | | | | D00392 | 3 | | | 275-278 |
| 159 | 24 | | PK | 4-10 | 25-31-31 | D06380J | | 6 | | | | | D00392 | 3 | | | 280-299 |
| 160 | 24 | | PK | 4-10 | 25-31-31 | D06380J | | 5 | | | | | D00392 | 4 | | | 275-278 |
| 160 | 24 | | PK | 4-10 | 25-31-31 | D06380J | | 9 | | | | | D00392 | 4 | | | 280-299 |
| 161 | 22 | | PA | 1-0 | 25-31-31 | D00392 | | 12 | | | | | D00392 | 11 | | | 275-299 |
| 163 | 16 | | PA | 2-0 | 25-31-31 | D04080J | | 30 | | FM | | | D06380J | 10 | | | 277-299 |
| 164 | 20 | | PA | 3-3 | 24-51-72 | D00254 | | 11 | | | | | D04080J | 39 | | | 050-099, 162-164, 276 |
| 165 | 20 | | PA | 3-3 | 24-51-72 | D00254 | | 12 | | | | | D04080J | 38 | | | 050-099, 162-164, 276 |
| 171 | 22 | | PA | 6-3 | 25-31-21 | D00390 | | 9 | | | | | TB0028Y | C013 | BJ | | 150-199, 275-299 |
| 172 | 16 | | PA | 1-9 | 25-31-21 | D04068J | | 10 | | | | | D04080J | 23 | | | 050-099, 150-199 |
| 172 | 16 | | PA | 2-10 | 25-31-21 | D04068J | | 10 | | | | | SM00001 | | W | | 275-276 |
| 173 | 16 | | PA | 3-3 | 25-31-31 | D06380J | | 10 | | | | | SM00001 | | W | | 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 8

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0022 | 286T0022 | | | | P31-L2-L.GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | |
| 179 | 22 | | PA | | 3-11 | 25-31-31 | D00392 | | 9 | | | | TB0028Y | C013 | BJ | | 275-299 |
| 401B | 24 | | PN | A | 3-11 | 24-23-11 | D04054J | | 10 | | | | D00280 | | 1 | | ALL |
| 401G | 24 | | PN | A | 0-0 | 24-23-11 | D04054J | | 11 | | | | D00280 | | 2 | | ALL |
| 401R | 24 | | PN | A | 0-0 | 24-23-11 | D04054J | | 12 | | | | D00280 | | 3 | | ALL |
| 401Y | 24 | | PN | A | 0-0 | 24-23-11 | D04054J | | 13 | | | | D00280 | | 4 | | ALL |
| 402B | 24 | | PN | B | 2-5 | 24-23-11 | D04054J | | 6 | | | | D00312 | | 1 | | ALL |
| 402G | 24 | | PN | B | 0-0 | 24-23-11 | D04054J | | 7 | | | | D00312 | | 2 | | ALL |
| 402R | 24 | | PN | B | 0-0 | 24-23-11 | D04054J | | 8 | | | | D00312 | | 3 | | ALL |
| 402Y | 24 | | PN | B | 0-0 | 24-23-11 | D04054J | | 9 | | | | D00312 | | 4 | | ALL |
| 403B | 24 | | PN | C | 3-9 | 24-23-12 | D04052J | | 1 | | | | D00282 | | 1 | | ALL |
| 403G | 24 | | PN | C | 0-0 | 24-23-12 | D04052J | | 2 | | | | D00282 | | 2 | | ALL |
| 403R | 24 | | PN | C | 0-0 | 24-23-12 | D04052J | | 3 | | | | D00282 | | 3 | | ALL |
| 403Y | 24 | | PN | C | 0-0 | 24-23-12 | D04052J | | 4 | | | | D00282 | | 4 | | ALL |
| W0024 | 286T0024 | | | | P32-R2-R GEN PWR DISTRIBUTION CONTROL | | | | | | | | | | | | |
| 001 | 24 | | PK | | 3-11 | 24-22-22 | D04012J | | 17 | | | | D00262 | | 3 | | ALL |
| 002 | 20 | | PA | | 3-0 | 24-22-22 | GDX0001 | | D.. | 2 | | | D00262 | | 4 | | ALL |
| 003 | 18 | | PA | | 4-9 | 24-22-21 | D04062J | | 10 | | | | C00903 | L2 | H | | ALL |
| 004 | 24 | | PK | | 5-3 | 24-22-21 | D04012J | | 18 | | | | D00260 | | 3 | | ALL |
| 005 | 20 | | PA | | 4-4 | 24-22-21 | GDX0001 | | D.. | 2 | | | D00260 | | 4 | | ALL |
| 006 | 20 | | PA | | 5-3 | 24-22-21 | D04012J | | 14 | | | | D00260 | | 39 | | ALL |
| 007 | 20 | | PA | | 4-4 | 24-22-21 | GDX0001 | | D.. | 2 | | | D00260 | | 40 | | ALL |
| 008 | 20 | | PA | | 5-3 | 24-22-21 | D04012J | | 15 | | | | D00260 | | 41 | | ALL |
| 009 | 20 | | PA | | 3-4 | 24-22-21 | D04012J | | 16 | | | | TB0032D | A006 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 009 | 20 | | PA | | 3-5 | 24-22-21 | D04012J | | 16 | | | | TB0032D | A006 | 2 | | 156-157, 166-199, 277-299 |
| 010 | 20 | | PA | | 4-2 | 24-22-21 | TB0032D | | C006 | 2 | | | D00260 | | 37 | | 050-099, 150-155, 162-165, 275-276 |
| 010 | 20 | | PA | | 4-3 | 24-22-21 | TB0032D | | C006 | 2 | | | D00260 | | 37 | | 156-157, 166-199, 277-299 |
| 011 | 20 | | PA | | 4-4 | 24-22-22 | D00260 | | 8 | | | | GDX0001 | D.. | 2 | | ALL |
| 012 | 24 | | PK | | 5-3 | 24-22-22 | D00260 | | 7 | | | | D04012J | | 22 | | ALL |
| 013 | 20 | | PA | | 3-0 | 24-22-22 | D00262 | | 8 | | | | GDX0001 | D.. | 2 | | ALL |
| 014 | 24 | | PK | | 3-11 | 24-22-22 | D00262 | | 7 | | | | D04012J | | 23 | | ALL |
| 015 | 18 | | PA | | 3-7 | 24-22-22 | C00904 | | L2 | H | | | D04062J | | 11 | | 050-099, 150-155, 162-165, 275-276 |
| 015 | 18 | | PA | | 3-8 | 24-22-22 | C00904 | | L2 | H | | | D04062J | | 11 | | 156-157, 166-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0020
Page 9
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0024 | 286T0024 | | | P32-R2-R GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | |
| 016 | 20 | | PA | 3-4 | 24-22-22 | TB0032D | A007 | 2 | | D04012J | 19 | | | 050-099, 150-155, 162-165, 275-276 | | |
| 016 | 20 | | PA | 3-5 | 24-22-22 | TB0032D | A007 | 2 | | D04012J | 19 | | | 156-157, 166-199, 277-299 | | |
| 017 | 20 | | PA | 2-10 | 24-22-22 | TB0032D | C007 | 2 | | D00262 | 37 | | | 050-099, 150-155, 162-165, 275-276 | | |
| 017 | 20 | | PA | 2-11 | 24-22-22 | TB0032D | C007 | 2 | | D00262 | 37 | | | 156-157, 166-199, 277-299 | | |
| 018 | 20 | | PA | 3-11 | 24-22-22 | D00262 | | 41 | | D04012J | 20 | | | ALL | | |
| 019 | 20 | | PA | 2-11 | 24-22-22 | D00262 | | 39 | | TB0034G | 7 | 2 | | 050-099, 150-155, 162-165, 275-276 | | |
| 019 | 20 | | PA | 3-0 | 24-22-22 | D00262 | | 39 | | TB0034G | 7 | 2 | | 156-157, 166-199, 277-299 | | |
| 020 | 20 | | PA | 3-0 | 24-22-22 | D00262 | | 40 | | GDX0001 | D.. | 2 | | ALL | | |
| 021 | 24 | | PK | 4-3 | 24-27-11 | D00260 | | 5 | | TB0032Y | A003 | BJ | | 050-099, 150-155, 162-165, 275-276 | | |
| 021 | 24 | | PK | 4-4 | 24-27-11 | D00260 | | 5 | | TB0032Y | A003 | BJ | | 156-157, 166-199, 277-299 | | |
| 022 | 24 | | PK | 3-10 | 24-27-11 | D00260 | | 6 | | D00262 | 23 | | | 050-099, 150-155, 162-165, 275-276 | | |
| 022 | 24 | | PK | 3-11 | 24-27-11 | D00260 | | 6 | | D00262 | 23 | | | 156-157, 166-199, 277-299 | | |
| 023 | 24 | | PK | 2-11 | 24-27-11 | TB0032Y | A003 | BJ | | D00262 | 21 | | | 050-099, 150-155, 162-165, 275-276 | | |
| 023 | 24 | | PK | 3-0 | 24-27-11 | TB0032Y | A003 | BJ | | D00262 | 21 | | | 156-157, 166-199, 277-299 | | |
| 024 | 24 | | PK | 3-1 | 24-27-11 | D04038J | | 1 | | TB0032Y | A003 | BJ | | 050-099, 150-155, 162-165, 275-276 | | |
| 024 | 24 | | PK | 3-2 | 24-27-11 | D04038J | | 1 | | TB0032Y | A003 | BJ | | 156-157, 166-199, 277-299 | | |
| 025 | 24 | | PK | 2-11 | 24-27-11 | TB0032Y | C003 | BJ | | D00262 | 22 | | | 050-099, 150-155, 162-165, 275-276 | | |
| 025 | 24 | | PK | 3-0 | 24-27-11 | TB0032Y | C003 | BJ | | D00262 | 22 | | | 156-157, 166-199, 277-299 | | |
| 026 | 24 | | PK | 2-11 | 24-27-11 | TB0032Y | C003 | BJ | | D00262 | 24 | | | 050-099, 150-155, 162-165, 275-276 | | |
| 026 | 24 | | PK | 3-0 | 24-27-11 | TB0032Y | C003 | BJ | | D00262 | 24 | | | 156-157, 166-199, 277-299 | | |

WIRE LIST
D280T132

91-21-11
Section W0020
Page 10
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0024 | 286T0024 | | | P32-R2-R GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | |
| 027 | 24 | | PK | 3-1 | 24-27-11 | TB0032Y | C003 | BJ | | D04038J | | 7 | | | 050-099, 150-155, 162-165, 275-276 | |
| 027 | 24 | | PK | 3-2 | 24-27-11 | TB0032Y | C003 | BJ | | D04038J | | 7 | | | 156-157, 166-199, 277-299 | |
| 028 | 24 | | PK | 3-2 | 24-27-21 | D04012J | | 34 | | TB0032Y | A012 | BJ | | | 050-099, 150-155, 162-165, 275-276 | |
| 028 | 24 | | PK | 3-4 | 24-27-21 | D04012J | | 34 | | TB0032Y | A012 | BJ | | | 156-157, 166-199, 277-299 | |
| 029 | 20 | | PA | 4-4 | 24-27-21 | GDX0001 | D.. | 2 | | D00260 | | 10 | | | ALL | |
| 030 | 24 | | PK | 3-2 | 24-27-21 | D04012J | | 35 | | TB0032Y | C011 | BJ | | | 050-099, 150-155, 162-165, 275-276 | |
| 030 | 24 | | PK | 3-4 | 24-27-21 | D04012J | | 35 | | TB0032Y | C011 | BJ | | | 156-157, 166-199, 277-299 | |
| 031 | 24 | | PK | 4-2 | 24-27-21 | TB0032G | | 5 | 2 | D00260 | | 2 | | | 050-099, 150-155, 162-165, 275-276 | |
| 031 | 24 | | PK | 4-3 | 24-27-21 | TB0032G | | 5 | 2 | D00260 | | 2 | | | 156-157, 166-199, 277-299 | |
| 032 | 24 | | PK | 2-10 | 24-27-21 | TB0032G | | 5 | 2 | D00262 | | 1 | | | 050-099, 150-155, 162-165, 275-276 | |
| 032 | 24 | | PK | 2-11 | 24-27-21 | TB0032G | | 5 | 2 | D00262 | | 1 | | | 156-157, 166-199, 277-299 | |
| 033 | 24 | | PK | 2-10 | 24-27-21 | TB0032G | | 5 | 2 | D00262 | | 15 | | | 050-099, 150-155, 162-165, 275-276 | |
| 033 | 24 | | PK | 2-11 | 24-27-21 | TB0032G | | 5 | 2 | D00262 | | 15 | | | 156-157, 166-199, 277-299 | |
| 034 | 24 | | PK | 2-11 | 24-27-21 | TB0032F | A001 | 2 | | D00262 | | 16 | | | 050-099, 150-155, 162-165, 275-276 | |
| 034 | 24 | | PK | 3-0 | 24-27-21 | TB0032F | A001 | 2 | | D00262 | | 16 | | | 156-157, 166-199, 277-299 | |
| 035 | 24 | | PK | 3-1 | 24-27-21 | TB0032F | A001 | 2 | | D04038J | | 8 | | | 050-099, 150-155, 162-165, 275-276 | |
| 035 | 24 | | PK | 3-2 | 24-27-21 | TB0032F | A001 | 2 | | D04038J | | 8 | | | 156-157, 166-199, 277-299 | |
| 036 | 20 | | PA | 3-0 | 24-27-21 | GDX0001 | D.. | 2 | | D00262 | | 2 | | | ALL | |
| 039 | 24 | | PK | 8-7 | 24-28-11 | D04012J | | 37 | | C00819 | | 2 | D | | 050-099, 150-155, 162-165, 275-276 | |
| 039 | 24 | | PK | 9-9 | 24-28-11 | D04012J | | 37 | | C00819 | | 2 | D | | 156-157, 166-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W0020
Page 11
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0024 | 286T0024 | | | P32-R2-R GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | | |
| 040 | 24 | | PK | 6-2 | 29-11-12 | D03452 | | 9 | | | | | TB0032Y | A004 | BJ | | 050-099, 150-155, 162-165, 275-276 |
| 040 | 24 | | PK | 6-3 | 29-11-12 | D03452 | | 9 | | | | | TB0032Y | A004 | BJ | | 156-157, 166-199, 277-299 |
| 041 | 24 | | PK | 2-8 | 24-41-12 | K00102 | | 12 | C | | | | D04038J | | 2 | | ALL |
| 042 | 24 | | PK | 2-8 | 24-41-12 | K00102 | | 13 | C | | | | D04038J | | 9 | | ALL |
| 043 | 20 | | PA | 4-9 | 24-51-23 | GDX0001 | | D.. | 2 | | | | K00120 | | 13 | C | 050-099, 150-155, 162-165, 275-276 |
| 043 | 20 | | PA | 4-8 | 24-51-23 | GDX0001 | | D.. | 2 | | | | K00120 | | 13 | C | 156-157, 166-199, 277-299 |
| 044 | 24 | | PK | 2-11 | 24-51-23 | K00120 | | 14 | C | | | | D04012J | | 39 | | ALL |
| 045 | 24 | | PK | 2-4 | 24-51-23 | K00120 | | X2 | C | | | | D04012J | | 33 | | ALL |
| 046 | 24 | | PK | 2-4 | 24-51-23 | K00120 | | X1 | C | | | | D04012J | | 38 | | ALL |
| 047 | 20 | | PA | 4-1 | 24-51-51 | GDX0001 | | D.. | 2 | | | | K00102 | | X2 | C | ALL |
| 048 | 24 | | PK | 2-0 | 24-51-51 | K00102 | | X1 | C | | | | D04012J | | 32 | | ALL |
| 053 | 24 | | PK | 0-7 | 29-11-31 | D03454 | | | 11 | | | | D03454 | | 12 | | ALL |
| 054 | 24 | | PK | 5-0 | 29-11-31 | TB0032Y | | C012 | BJ | | | | D03454 | | 1 | | 050-099, 150-155, 162-165, 275-276 |
| 054 | 24 | | PK | 5-2 | 29-11-31 | TB0032Y | | C012 | BJ | | | | D03454 | | 1 | | 156-157, 166-199, 277-299 |
| 055 | 24 | | PK | 5-0 | 29-11-31 | TB0032Y | | C012 | BJ | | | | D03454 | | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 055 | 24 | | PK | 5-2 | 29-11-31 | TB0032Y | | C012 | BJ | | | | D03454 | | 2 | | 156-157, 166-199, 277-299 |
| 056 | 24 | | PK | 5-0 | 29-11-31 | TB0032Y | | C012 | BJ | | | | D03454 | | 3 | | 050-099, 150-155, 162-165, 275-276 |
| 056 | 24 | | PK | 5-2 | 29-11-31 | TB0032Y | | C012 | BJ | | | | D03454 | | 3 | | 156-157, 166-199, 277-299 |
| 057 | 24 | | PK | 5-3 | 29-11-31 | TB0032Y | | C004 | BJ | | | | D03454 | | 10 | | 050-099, 150-155, 162-165, 275-276 |
| 057 | 24 | | PK | 5-4 | 29-11-31 | TB0032Y | | C004 | BJ | | | | D03454 | | 10 | | 156-157, 166-199, 277-299 |
| 058 | 24 | | PK | 4-1 | 29-11-31 | M00304 | | | B C | | | | D03454 | | 8 | | ALL |
| 060 | 22 | | PA | 3-5 | 29-32-11 | TB0032F | | A002 | 2 | | | | D04012J | | 41 | | 050-099, 150-155, 162-165, 275-276 |
| 060 | 22 | | PA | 3-6 | 29-32-11 | TB0032F | | A002 | 2 | | | | D04012J | | 41 | | 156-157, 166-199, 277-299 |
| 063 | 24 | | PK | 0-7 | 29-11-12 | D03452 | | | 11 | | | | D03452 | | 12 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 12

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0024 | 286T0024 | | | P32-R2-R GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | |
| 064 | 24 | | PK | 5-5 | 29-11-12 | TB0032Y | A011 | BJ | | D03452 | | | 1 | | 050-099, 150-155, 162-165, 275-276 | |
| 064 | 24 | | PK | 6-1 | 29-11-12 | TB0032Y | A011 | BJ | | D03452 | | | 1 | | 156-157, 166-199, 277-299 | |
| 065 | 24 | | PK | 5-5 | 29-11-12 | TB0032Y | A011 | BJ | | D03452 | | | 2 | | 050-099, 150-155, 162-165, 275-276 | |
| 065 | 24 | | PK | 6-1 | 29-11-12 | TB0032Y | A011 | BJ | | D03452 | | | 2 | | 156-157, 166-199, 277-299 | |
| 066 | 24 | | PK | 5-5 | 29-11-12 | TB0032Y | A011 | BJ | | D03452 | | | 3 | | 050-099, 150-155, 162-165, 275-276 | |
| 066 | 24 | | PK | 6-1 | 29-11-12 | TB0032Y | A011 | BJ | | D03452 | | | 3 | | 156-157, 166-199, 277-299 | |
| 067 | 20 | | PA | 6-3 | 29-11-12 | D03452 | | | 15 | GDX0002 | | A.. | 2 | | ALL | |
| 068 | 24 | | PK | 5-3 | 29-11-31 | D03454 | | | 9 | TB0032Y | | C004 | BJ | | 050-099, 150-155, 162-165, 275-276 | |
| 068 | 24 | | PK | 5-4 | 29-11-31 | D03454 | | | 9 | TB0032Y | | C004 | BJ | | 156-157, 166-199, 277-299 | |
| 069 | 24 | | PK | 6-2 | 29-11-12 | TB0032Y | A004 | BJ | | D03452 | | | 10 | | 050-099, 150-155, 162-165, 275-276 | |
| 069 | 24 | | PK | 6-3 | 29-11-12 | TB0032Y | A004 | BJ | | D03452 | | | 10 | | 156-157, 166-199, 277-299 | |
| 070 | 24 | | PK | 3-5 | 29-11-12 | D04012J | | | 7 | TB0034G | | | 3 | 2 | 050-099, 150-155, 162-165, 275-276 | |
| 070 | 24 | | PK | 3-6 | 29-11-12 | D04012J | | | 7 | TB0034G | | | 3 | 2 | 156-157, 166-199, 277-299 | |
| 071 | 20 | | PA | 5-4 | 29-11-31 | D03454 | | | 15 | GDX0002 | | A.. | 2 | | ALL | |
| 072 | 24 | | PK | 4-5 | 25-31-11 | D00378 | | | 1 | D04012J | | | 9 | | ALL | |
| 073 | 24 | | PK | 4-5 | 25-31-11 | D00378 | | | 2 | D04012J | | | 10 | | ALL | |
| 074 | 24 | | PK | 4-5 | 25-31-11 | D00378 | | | 3 | D04012J | | | 11 | | ALL | |
| 075 | 24 | | PK | 4-5 | 25-31-11 | D00378 | | | 4 | D04012J | | | 12 | | ALL | |
| 076 | 22 | | PA | 0-7 | 25-31-11 | D00378 | | | 11 | D00378 | | | 13 | | 050-099, 150-199 | |
| 076 | 22 | | PA | 0-7 | 25-31-11 | D00378 | | | 11 | D00378 | | | 14 | | 275-299 | |
| 078 | 20 | | PA | 4-8 | 25-31-11 | D04038J | | | 21 | D00378 | | | 8 | | 050-099 | |
| 078 | 20 | | PA | 4-8 | 25-31-11 | D04038J | | | 20 | D00378 | | | 8 | | 150-154 | |
| 078 | 20 | | PA | 6-11 | 25-31-11 | TB0034G | | | 1 | D00378 | | | 8 | | 155-199 | |
| 079 | 20 | | PA | 3-2 | 25-31-11 | TB0034G | | | 1 | D04038J | | | 22 | | 155-199 | |
| 079 | 20 | | PA | 4-8 | 25-31-11 | D00378 | | | 8 | D04062J | | | 2 | | 275-276 | |
| 079 | 20 | | PA | 4-8 | 25-31-11 | D00378 | | | 8 | D04038J | | | 22 | | 277-278 | |
| 079 | 18 | | PA | 4-8 | 25-31-11 | D00378 | | | 8 | D04038J | | | 22 | DK | 280-299 | |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 13

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0024 | 286T0024 | | | P32-R2-R GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | | |
| 081 | 22 | | PA | 6-11 | 25-31-11 | D00378 | | 9 | | | | | TB0034G | 2 | 2 | | 280-299 |
| 084 | 22 | | PA | 3-5 | 25-31-11 | TB0034G | | 2 | 2 | | | | D04012J | 5 | | | 050-099, 150-155, 162-165 |
| 084 | 22 | | PA | 3-6 | 25-31-11 | TB0034G | | 2 | 2 | | | | D04012J | 5 | | | 156-157, 166-199, 280-299 |
| 084 | 22 | | PA | 4-5 | 25-31-11 | D00378 | | 9 | | | | | D04012J | 5 | | | 275-278 |
| 098 | 20 | | PA | 4-11 | 24-22-12 | D04038J | | 11 | | | | | D00260 | 14 | | | ALL |
| 099 | 24 | | PK | 3-2 | 24-22-12 | D04038J | | 10 | | | | | TB0034G | 5 | 2 | | ALL |
| 100 | 24 | | PK | 3-2 | 24-22-12 | D04038J | | 12 | | | | | TB0034G | 5 | 2 | | ALL |
| 101 | 24 | | PK | 4-3 | 24-22-12 | TB0034G | | 5 | 2 | | | | D00260 | 22 | | | 050-099, 150-155, 162-165, 275-276 |
| 101 | 24 | | PK | 4-4 | 24-22-12 | TB0034G | | 5 | 2 | | | | D00260 | 22 | | | 156-157, 166-199, 277-299 |
| 102 | 20 | | PA | 4-11 | 24-22-12 | D04038J | | 14 | | | | | D00260 | 13 | | | ALL |
| 103 | 24 | | PK | 4-11 | 24-22-12 | D04038J | | 13 | | | | | D00260 | 21 | | | ALL |
| 104 | 24 | | PK | 3-7 | 24-51-31 | D04038J | | 15 | | | | | D00262 | 27 | | | ALL |
| 105 | 24 | | PK | 3-7 | 24-51-31 | D04038J | | 16 | | | | | D00262 | 28 | | | ALL |
| 106 | 20 | | PA | 3-6 | 24-22-22 | D04012J | | 21 | | | | | D00416 | A3 | | | 050-099, 150-155, 162-165, 275-276 |
| 106 | 20 | | PA | 3-8 | 24-22-22 | D04012J | | 21 | | | | | D00416 | A3 | | | 156-157, 166-199, 277-299 |
| 107 | 24 | | PK | 2-11 | 24-51-31 | D00262 | | 25 | | | | | TB0034G | 6 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 107 | 24 | | PK | 3-0 | 24-51-31 | D00262 | | 25 | | | | | TB0034G | 6 | 2 | | 156-157, 166-199, 277-299 |
| 108 | 24 | | PK | 4-3 | 24-51-31 | D00260 | | 28 | | | | | TB0034G | 6 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 108 | 24 | | PK | 4-4 | 24-51-31 | D00260 | | 28 | | | | | TB0034G | 6 | 2 | | 156-157, 166-199, 277-299 |
| 109 | 20 | | PA | 4-3 | 24-22-22 | D00260 | | 18 | | | | | TB0034G | 7 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 109 | 20 | | PA | 4-4 | 24-22-22 | D00260 | | 18 | | | | | TB0034G | 7 | 2 | | 156-157, 166-199, 277-299 |
| 110 | 20 | | PA | 4-2 | 24-22-22 | D00260 | | 17 | | | | | TB0034G | 8 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 110 | 20 | | PA | 4-3 | 24-22-22 | D00260 | | 17 | | | | | TB0034G | 8 | 2 | | 156-157, 166-199, 277-299 |
| 111 | 24 | | PK | 4-2 | 24-51-31 | D00260 | | 27 | | | | | TB0034G | 9 | 2 | | 050-099, 150-155, 162-165, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 14

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0024 | 286T0024 | | | P32-R2-R GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | |
| 111 | 24 | | PK | 4-3 | 24-51-31 | D00260 | | 27 | | | TB0034G | 9 | 2 | | 156-157, 166-199, 277-299 | |
| 112 | 20 | | PA | 1-9 | 24-51-31 | D00416 | | X2 | | | GDX0002 | D.. | 2 | | 050-099, 150-155, 162-165, 275-276 | |
| 112 | 20 | | PA | 1-11 | 24-51-31 | D00416 | | X2 | | | GDX0002 | D.. | 2 | | 156-157, 166-199, 277-299 | |
| 113 | 24 | | PK | 1-7 | 24-51-31 | D00416 | | X1 | | | TB0034G | 9 | 2 | | 050-099, 150-155, 162-165, 275-276 | |
| 113 | 24 | | PK | 1-10 | 24-51-31 | D00416 | | X1 | | | TB0034G | 9 | 2 | | 156-157, 166-199, 277-299 | |
| 114 | 24 | | PK | 1-7 | 24-51-31 | D00416 | | B2 | | | TB0034G | 9 | 2 | | 050-099, 150-155, 162-165, 275-276 | |
| 114 | 24 | | PK | 1-10 | 24-51-31 | D00416 | | B2 | | | TB0034G | 9 | 2 | | 156-157, 166-199, 277-299 | |
| 115 | 20 | | PA | 1-7 | 24-22-22 | D00416 | | A2 | | | TB0034G | 8 | 2 | | 050-099, 150-155, 162-165, 275-276 | |
| 115 | 20 | | PA | 1-10 | 24-22-22 | D00416 | | A2 | | | TB0034G | 8 | 2 | | 156-157, 166-199, 277-299 | |
| 116 | 24 | | PK | 3-5 | 24-51-31 | D04012J | | 42 | | | TB0034G | 6 | 2 | | 050-099, 150-155, 162-165, 275-276 | |
| 116 | 24 | | PK | 3-6 | 24-51-31 | D04012J | | 42 | | | TB0034G | 6 | 2 | | 156-157, 166-199, 277-299 | |
| 117 | 20 | | PA | 3-5 | 24-22-22 | D04012J | | 43 | | | TB0034G | 7 | 2 | | 050-099, 150-155, 162-165, 275-276 | |
| 117 | 20 | | PA | 3-6 | 24-22-22 | D04012J | | 43 | | | TB0034G | 7 | 2 | | 156-157, 166-199, 277-299 | |
| 118 | 24 | | PK | 3-4 | 24-51-31 | D04012J | | 44 | | | TB0034G | 9 | 2 | | 050-099, 150-155, 162-165, 275-276 | |
| 118 | 24 | | PK | 3-5 | 24-51-31 | D04012J | | 44 | | | TB0034G | 9 | 2 | | 156-157, 166-199, 277-299 | |
| 119 | 20 | | PA | 3-4 | 24-22-22 | D04012J | | 45 | | | TB0034G | 8 | 2 | | 050-099, 150-155, 162-165, 275-276 | |
| 119 | 20 | | PA | 3-5 | 24-22-22 | D04012J | | 45 | | | TB0034G | 8 | 2 | | 156-157, 166-199, 277-299 | |
| 120 | 24 | | PK | 2-8 | 29-11-31 | D00262 | | 17 | | | TB0032G | 10 | 2 | | 050-099, 150-155, 162-165, 275-276 | |
| 120 | 24 | | PK | 2-9 | 29-11-31 | D00262 | | 17 | | | TB0032G | 10 | 2 | | 156-157, 166-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W0020
Page 15
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0024 | 286T0024 | | | P32-R2-R GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | | |
| 121 | 24 | | PK | 2-5 | 29-11-31 | D00262 | | 18 | | | | | M00304 | A | C | *1 | 050-099, 150-155, 162-165, 275-276 |
| 121 | 24 | | PK | 3-0 | 29-11-31 | D00262 | | 18 | | | | | M00304 | A | C | *1 | 156-157, 166-199, 277-299 |
| 122 | 24 | | PK | 2-5 | 29-11-31 | D00262 | | 20 | | | | | M00304 | A | C | *1 | 050-099, 150-155, 162-165, 275-276 |
| 122 | 24 | | PK | 3-0 | 29-11-31 | D00262 | | 20 | | | | | M00304 | A | C | *1 | 156-157, 166-199, 277-299 |
| 123 | 24 | | PK | 2-9 | 29-11-31 | D00262 | | 19 | | | | | TB0034G | 11 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 123 | 24 | | PK | 2-10 | 29-11-31 | D00262 | | 19 | | | | | TB0034G | 11 | 2 | | 156-157, 166-199, 277-299 |
| 124 | 24 | | PK | 3-3 | 29-11-31 | D04012J | | 46 | | | | | TB0034G | 11 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 124 | 24 | | PK | 3-4 | 29-11-31 | D04012J | | 46 | | | | | TB0034G | 11 | 2 | | 156-157, 166-199, 277-299 |
| 125 | 24 | | PK | 6-0 | 29-11-31 | D03452 | | 5 | | | | | TB0034G | 11 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 125 | 24 | | PK | 6-1 | 29-11-31 | D03452 | | 5 | | | | | TB0034G | 11 | 2 | | 156-157, 166-199, 277-299 |
| 126 | 24 | | PK | 3-9 | 29-11-31 | D03452 | | 6 | | | | | D04012J | 48 | | | ALL |
| 127 | 20 | | PA | 7-0 | 25-31-11 | D00378 | | 10 | | | | | GDX0002 | D.. | 2 | | ALL |
| 128 | 20 | | PA | 7-0 | 25-31-11 | D00378 | | 15 | | | | | GDX0002 | S.. | 2 | | ALL |
| 131 | 20 | | PA | 2-7 | 29-11-31 | M00304 | | G | | | | | GDX0002 | D.. | 2 | | ALL |
| 133 | 24 | | PK | 3-9 | 24-51-31 | D04062J | | 7 | | | | | D00262 | 26 | | | ALL |
| 134 | 24 | | PK | 1-5 | 24-51-31 | D00416 | | B1 | | | | | TB0032D | A008 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 134 | 24 | | PK | 1-9 | 24-51-31 | D00416 | | B1 | | | | | TB0032D | A008 | 2 | | 156-157, 166-199, 277-299 |
| 135 | 24 | | PK | 3-0 | 24-51-31 | D04062J | | 5 | | | | | TB0032D | C008 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 135 | 24 | | PK | 3-2 | 24-51-31 | D04062J | | 5 | | | | | TB0032D | C008 | 2 | | 156-157, 166-199, 277-299 |
| 136 | 22 | | PA | 0-7 | 25-31-11 | D00378 | | 16 | | | | | D00378 | 17 | | | ALL |
| 138 | 24 | | PK | 2-8 | 24-51-52 | D04012J | | 49 | | | | | K00120 | 14 | C | | ALL |
| 141 | 24 | | PK | 3-11 | 24-22-22 | D04012J | | 8 | | | | | D00262 | 9 | | | ALL |
| 142 | 20 | | PA | 3-0 | 24-22-22 | D00262 | | 10 | | | | | GDX0001 | D.. | 2 | | ALL |
| 143 | 24 | | PK | 3-7 | 24-51-71 | D00262 | | 5 | | | | | D04038J | 18 | | | ALL |
| 144 | 24 | | PK | 3-7 | 24-51-71 | D00262 | | 6 | | | | | D04038J | 17 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 16

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0024 | 286T0024 | | | P32-R2-R GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | |
| 145 | 24 | | PK | 5-3 | 24-51-71 | D00260 | | 25 | | | D04012J | | 50 | | | ALL |
| 146 | 24 | | PK | 5-3 | 24-51-71 | D00260 | | 26 | | | D04012J | | 4 | | | ALL |
| 147 | 24 | | PK | 3-2 | 24-27-21 | D04012J | | 51 | | | TB0032Y | A012 | BJ | | | 050-099, 150-155, 162-165, 275-276 |
| 147 | 24 | | PK | 3-4 | 24-27-21 | D04012J | | 51 | | | TB0032Y | A012 | BJ | | | 156-157, 166-199, 277-299 |
| 148 | 24 | | PK | 4-0 | 24-27-21 | D00260 | | 9 | | | TB0032Y | A012 | BJ | | | 050-099, 150-155, 162-165, 275-276 |
| 148 | 24 | | PK | 4-1 | 24-27-21 | D00260 | | 9 | | | TB0032Y | A012 | BJ | | | 156-157, 166-199, 277-299 |
| 149 | 24 | | PK | 3-2 | 24-27-21 | D04012J | | 52 | | | TB0032Y | C011 | BJ | | | 050-099, 150-155, 162-165, 275-276 |
| 149 | 24 | | PK | 3-4 | 24-27-21 | D04012J | | 52 | | | TB0032Y | C011 | BJ | | | 156-157, 166-199, 277-299 |
| 150 | 24 | | PK | 4-0 | 24-27-21 | D00260 | | 1 | | | TB0032Y | C011 | BJ | | | 050-099, 150-155, 162-165, 275-276 |
| 150 | 24 | | PK | 4-1 | 24-27-21 | D00260 | | 1 | | | TB0032Y | C011 | BJ | | | 156-157, 166-199, 277-299 |
| 151 | 22 | | PA | 6-11 | 25-31-11 | D00378 | | 9 | | | TB0034G | 2 | 2 | | | 050-099, 150-199 |
| 156 | 20 | | PA | 4-4 | 25-31-12 | D13450 | | 8 | | | D04038J | 22 | | | | 050-099, 150-154 |
| 156 | 20 | | PA | 6-7 | 25-31-12 | D13450 | | 8 | | | TB0034G | 1 | 2 | | | 155-199 |
| 157 | 24 | | PK | 3-5 | 29-11-12 | D04012J | | 3 | | | TB0032Y | A004 | BJ | | | 050-099, 150-155, 162-165, 275-276 |
| 157 | 24 | | PK | 3-6 | 29-11-12 | D04012J | | 3 | | | TB0032Y | A004 | BJ | | | 156-157, 166-199, 277-299 |
| 158 | 24 | | PK | 3-9 | 29-11-12 | D04012J | | 36 | | | D03452 | 18 | | | | ALL |
| 159 | 24 | | PK | 3-2 | 29-11-31 | D04012J | | 47 | | | TB0032G | 10 | 2 | | | 050-099, 150-155, 162-165, 275-276 |
| 159 | 24 | | PK | 3-4 | 29-11-31 | D04012J | | 47 | | | TB0032G | 10 | 2 | | | 156-157, 166-199, 277-299 |
| 160 | 24 | | PK | 5-0 | 29-11-31 | D03454 | | 18 | | | TB0032G | 10 | 2 | | | 050-099, 150-155, 162-165, 275-276 |
| 160 | 24 | | PK | 5-2 | 29-11-31 | D03454 | | 18 | | | TB0032G | 10 | 2 | | | 156-157, 166-199, 277-299 |
| 161 | 24 | | PK | 3-3 | 29-11-31 | D04062J | | 16 | | | TB0032Y | C004 | BJ | | | ALL |
| 165 | 22 | | PA | 6-7 | 25-31-12 | D13450 | | 9 | | | TB0034G | 2 | 2 | | | 050-099, 150-199 |
| 166 | 22 | | PA | 0-7 | 25-31-12 | D13450 | | 11 | | | D13450 | 12 | | | | 050-099, 150-199 |
| 167 | 20 | | PA | 6-8 | 25-31-12 | D13450 | | 10 | | | GDX0002 | D.. | 2 | | | 050-099, 150-199 |
| 168 | 20 | | PA | 6-8 | 25-31-12 | D13450 | | 15 | | | GDX0002 | S.. | 2 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 17

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0024 | 286T0024 | | | P32-R2-R GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | | |
| 169 | 18 | | PA | | 1-9 | 25-31-12 | D08686J | | 10 | | | | D04062J | 15 | | | 050-099, 150-199 |
| 170 | 22 | | PA | | 0-7 | 25-31-12 | D13450 | | 16 | | | | D13450 | 17 | | | 050-099, 150-199 |
| 171 | 24 | | PK | | 4-7 | 25-31-12 | D13450 | | 1 | | | | D08686J | 8 | | | 050-099, 150-199 |
| 172 | 24 | | PK | | 4-7 | 25-31-12 | D13450 | | 2 | | | | D08686J | 5 | | | 050-099, 150-199 |
| 174 | 24 | | PK | | 4-7 | 25-31-12 | D13450 | | 3 | | | | D08686J | 6 | | | 050-099, 150-199 |
| 175 | 24 | | PK | | 4-7 | 25-31-12 | D13450 | | 4 | | | | D08686J | 9 | | | 050-099, 150-199 |
| 176 | 24 | | PK | | 6-2 | 29-11-12 | D03452 | | 8 | | | | TB0034G | 3 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 176 | 24 | | PK | | 6-3 | 29-11-12 | D03452 | | 8 | | | | TB0034G | 3 | 2 | | 156-157, 166-199, 277-299 |
| 177 | 24 | | PK | | 3-5 | 31-31-26 | TB0034G | | 3 | 2 | | | D04012J | 53 | | | 050-099, 150-155, 162-165, 275-276 |
| 177 | 24 | | PK | | 3-6 | 31-31-26 | TB0034G | | 3 | 2 | | | D04012J | 53 | | | 156-157, 166-199, 277-299 |
| 179 | 24 | | PK | | 2-3 | 31-31-26 | M00304 | | B | C | | | D04012J | 54 | | | ALL |
| 180 | 18 | | PA | | 2-11 | 30-71-25 | D04038J | | 19 | DK | | | TB0032G | 9 | 2 | | 050-099, 150-155, 162-165 |
| 180 | 18 | | PA | | 3-0 | 30-71-25 | D04038J | | 19 | DK | | | TB0032G | 9 | 2 | | 156-157, 166-199 |
| 181 | 18 | | PA | | 2-9 | 30-71-25 | D08686J | | 4 | | | | TB0032G | 9 | 2 | | 050-099, 150-155, 162-165 |
| 181 | 18 | | PA | | 2-10 | 30-71-25 | D08686J | | 4 | | | | TB0032G | 9 | 2 | | 156-157, 166-199 |
| 182 | 18 | | PA | | 3-0 | 30-71-25 | D04062J | | 8 | | | | TB0032G | 9 | 2 | | 050-099, 150-155, 162-165 |
| 182 | 18 | | PA | | 3-2 | 30-71-25 | D04062J | | 8 | | | | TB0032G | 9 | 2 | | 156-157, 166-199 |
| 183 | 18 | | PA | | 3-0 | 30-71-25 | D04062J | | 9 | | | | TB0032G | 9 | 2 | | 050-099, 150-155, 162-165 |
| 183 | 18 | | PA | | 3-2 | 30-71-25 | D04062J | | 9 | | | | TB0032G | 9 | 2 | | 156-157, 166-199 |
| 188 | 20 | | PA | | 3-11 | 24-51-72 | D00262 | | 11 | | | | D04012J | 40 | | | 050-099, 162-164, 276 |
| 189 | 20 | | PA | | 3-0 | 24-51-72 | D00262 | | 12 | | | | GDX0001 | D.. | 2 | | 050-099, 162-164, 276 |
| 301B | 18 | | PC | D | 6-1 | 24-21-21 | C00903 | | T1 | H | | | D04062J | 12 | | | 050-099, 150-155, 162-165, 275-276 |
| 301B | 18 | | PC | D | 5-5 | 24-21-21 | C00903 | | T1 | H | | | D04062J | 12 | | | 156-157, 166-199, 277-299 |
| 301R | 18 | | PC | D | 0-0 | 24-21-21 | C00903 | | T2 | H | | | D04062J | 13 | | | ALL |
| 301Y | 18 | | PC | D | 0-0 | 24-21-21 | C00903 | | T3 | H | | | D04062J | 14 | | | ALL |
| 401B | 24 | | PN | A | 4-5 | 24-23-11 | D00284 | | 1 | | | | D04012J | 24 | | | 050-099, 150-155, 162-165, 275-276 |
| 401B | 24 | | PN | A | 4-3 | 24-23-11 | D00284 | | 1 | | | | D04012J | 24 | | | 156-157, 166-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 18

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|---|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0024 | 286T0024 | P32-R2-R GEN PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | | | |
| 401G | 24 | PN | A | 0-0 | 24-23-11 | D00284 | | 4 | | | | D04012J | 27 | | ALL | |
| 401R | 24 | PN | A | 0-0 | 24-23-11 | D00284 | | 2 | | | | D04012J | 25 | | ALL | |
| 401Y | 24 | PN | A | 0-0 | 24-23-11 | D00284 | | 3 | | | | D04012J | 26 | | ALL | |
| 402B | 24 | PN | B | 1-8 | 24-23-11 | D00306 | | 1 | | | | D04012J | 28 | | ALL | |
| 402G | 24 | PN | B | 0-0 | 24-23-11 | D00306 | | 4 | | | | D04012J | 31 | | ALL | |
| 402R | 24 | PN | B | 0-0 | 24-23-11 | D00306 | | 2 | | | | D04012J | 29 | | ALL | |
| 402Y | 24 | PN | B | 0-0 | 24-23-11 | D00306 | | 3 | | | | D04012J | 30 | | ALL | |
| 403B | 24 | PN | C | 4-2 | 24-23-12 | D00286 | | 1 | | | | D04038J | 3 | | 050-099, 150-155, 162-165, 275-276 156-157, 166-199, 277-299 | |
| 403B | 24 | PN | C | 4-4 | 24-23-12 | D00286 | | 1 | | | | D04038J | 3 | | ALL | |
| 403G | 24 | PN | C | 0-0 | 24-23-12 | D00286 | | 2 | | | | D04038J | 4 | | ALL | |
| 403R | 24 | PN | C | 0-0 | 24-23-12 | D00286 | | 3 | | | | D04038J | 5 | | ALL | |
| 403Y | 24 | PN | C | 0-0 | 24-23-12 | D00286 | | 4 | | | | D04038J | 6 | | ALL | |
| W0026 | 286T0026 | P34-A2-APU PWR DISTRIBUTION CONTROL | | | | | | | | | | | | | | |
| 005 | 22 | PA | | 1-5 | 49-61-11 | D04112J | | 25 | | | | D04028J | 14 | | ALL | |
| 006 | 22 | PA | | 1-5 | 49-61-11 | D04112J | | 26 | | | | D04028J | 15 | | ALL | |
| 007 | 22 | PA | | 1-5 | 49-61-11 | D04112J | | 27 | | | | D04028J | 5 | | ALL | |
| 008 | 22 | PA | | 1-5 | 49-61-11 | D04112J | | 28 | | | | D04028J | 6 | | ALL | |
| 010 | 24 | PK | | 4-3 | 24-41-12 | D00274 | | 2 | | | | D04028J | 13 | | ALL | |
| 011 | 24 | PK | | 4-10 | 24-27-11 | D04028J | | 12 | | | | D00268 | 5 | | ALL | |
| 012 | 22 | PA | | 3-10 | 49-61-11 | D04112J | | 29 | | | | TB0024G | 17 | 2 | ALL | |
| 015 | 24 | PK | | 4-4 | 24-28-11 | D05340J | | 4 | | | | TB0024F | A006 | 2 | ALL | |
| 016 | 24 | PK | | 4-4 | 24-28-11 | D05340J | | 3 | | | | TB0024F | A008 | 2 | ALL | |
| 019 | 24 | PK | | 3-11 | 24-41-12 | D04112J | | 21 | | | | D00274 | 3 | | ALL | |
| 021 | 24 | PK | | 3-4 | 24-51-51 | D04112J | | 36 | | | | K00103 | X1 | C | ALL | |
| 026 | 18 | PA | | 4-1 | 33-31-31 | D04028J | | 34 | DK | | | TB0024F | A007 | 2 | ALL | |
| 027 | 18 | PA | | 3-8 | 24-28-11 | C00905 | | T2 | H | *2 | | TB0024F | C006 | 2 | ALL | |
| 028 | 18 | PA | | 3-10 | 24-21-41 | C00905 | | T3 | H | *3 | | L00135 | 1 | C | ALL | |
| 029 | 20 | PA | | 3-11 | 24-22-41 | D00268 | | 37 | | | | TB0024D | C001 | 2 | ALL | |
| 030 | 20 | PA | | 2-0 | 24-51-51 | K00103 | | X2 | C | | | GDX0001 | D.. | 2 | ALL | |
| 031 | 20 | PA | | 2-10 | 24-51-61 | K00101 | | X2 | C | | | GDX0001 | D.. | 2 | ALL | |
| 032 | 24 | PK | | 3-3 | 24-51-61 | K00101 | | Y2 | C | | | TB0024F | C007 | 2 | ALL | |
| 033 | 18 | PA | | 6-0 | 24-22-41 | D04026J | | 1 | | | | C00905 | L2 | H | ALL | |
| 034 | 24 | PK | | 4-6 | 24-22-41 | D04112J | | 1 | | | | D00268 | 3 | | ALL | |
| 035 | 24 | PK | | 4-6 | 24-41-11 | D04112J | | 2 | | | | D00268 | 7 | | ALL | |
| 036 | 24 | PK | | 3-11 | 24-41-11 | D04112J | | 3 | | | | D00274 | 7 | | ALL | |
| 037 | 24 | PK | | 3-10 | 24-41-11 | D04112J | | 4 | | | | TB0024F | C005 | 2 | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 19

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0026 | 286T0026 | | | P34-A2-APU PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | | |
| 038 | 24 | | PK | 3-10 | 24-41-11 | D04112J | | 5 | | | | | TB0024F | C004 | 2 | | ALL |
| 039 | 24 | | PK | 3-10 | 24-41-11 | D04112J | | 6 | | | | | TB0024F | C003 | 2 | | ALL |
| 042 | 24 | | PK | 4-6 | 24-27-21 | D04112J | | 9 | | | | | D00268 | 1 | | | ALL |
| 043 | 20 | | PA | 4-6 | 24-22-41 | D04112J | | 10 | | | | | D00268 | 39 | | | ALL |
| 044 | 20 | | PA | 4-6 | 24-22-41 | D04112J | | 11 | | | | | D00268 | 41 | | | ALL |
| 045 | 20 | | PA | 3-10 | 24-22-41 | D04112J | | 12 | | | | | TB0024D | A001 | 2 | | ALL |
| 046 | 20 | | PA | 3-11 | 24-41-11 | D04112J | | 13 | | | | | D00274 | 40 | | | ALL |
| 047 | 24 | | PK | 4-2 | 24-51-61 | D04112J | | 14 | | | | | K00101 | X1 | C | | ALL |
| 048 | 24 | | PK | 3-11 | 24-51-61 | D04112J | | 15 | | | | | K00101 | Y1 | C | | ALL |
| 049 | 18 | | PA | 3-10 | 24-21-51 | K00114 | | C2 | H | | | | L00124 | 1 | C | | ALL |
| 050 | 16 | | PA | 3-9 | 24-41-11 | K00114 | | A1 | H | | | | L00081 | 1 | C | | ALL |
| 051 | 22 | | PA | 4-1 | 49-61-11 | D04028J | | 7 | | | | | TB0024G | 17 | 2 | | 050-099, 150-199 |
| 051 | 22 | | PA | 4-1 | 49-61-11 | TB0024G | | 17 | 2 | | | | D04028J | 7 | | | 275-299 |
| 056 | 16 | | PA | 3-4 | 24-41-11 | K00114 | | C1 | H | | | | TB0024F | A005 | 2 | | ALL |
| 057 | 16 | | PA | 3-5 | 24-41-11 | K00114 | | B1 | H | | | | TB0024F | A004 | 2 | | ALL |
| 058 | 16 | | PA | 3-5 | 24-41-11 | K00114 | | A1 | H | | | | TB0024F | A003 | 2 | | ALL |
| 059 | 20 | | PA | 2-7 | 24-41-12 | D00274 | | 1 | | | | | GDX0001 | D.. | 2 | | ALL |
| 060 | 20 | | PA | 2-7 | 24-41-12 | D00274 | | 4 | | | | | GDX0001 | D.. | 2 | | ALL |
| 061 | 18 | | PA | 2-10 | 24-21-41 | L00135 | | 2 | C | | | | GDX0002 | A.. | 2 | | ALL |
| 062 | 18 | | PA | 2-10 | 24-21-51 | L00124 | | 2 | C | | | | GDX0002 | A.. | 2 | | ALL |
| 063 | 16 | | PA | 2-10 | 24-41-11 | L00081 | | 2 | C | | | | GDX0002 | A.. | 2 | | ALL |
| 064 | 22 | | PA | 4-1 | 49-61-11 | TB0024D | | C013 | 2 | | | | D04028J | 24 | | | ALL |
| 065 | 20 | | PA | 3-2 | 24-22-41 | D00268 | | 4 | | | | | GDX0001 | D.. | 2 | | ALL |
| 066 | 20 | | PA | 3-2 | 24-22-41 | D00268 | | 40 | | | | | GDX0001 | D.. | 2 | | ALL |
| 067 | 20 | | PA | 2-7 | 24-27-11 | D00274 | | 10 | | | | | GDX0001 | D.. | 2 | | ALL |
| 068 | 24 | | PK | 3-5 | 24-27-11 | D00274 | | 9 | | | | | D00268 | 6 | | | ALL |
| 069 | 24 | | PK | 3-5 | 24-27-21 | D00274 | | 5 | | | | | D00268 | 2 | | | ALL |
| 070 | 20 | | PA | 2-7 | 24-27-21 | D00274 | | 6 | | | | | GDX0001 | D.. | 2 | | ALL |
| 072 | 20 | | PA | 2-7 | 24-41-11 | D00274 | | 8 | | | | | GDX0001 | D.. | 2 | | ALL |
| 073 | 20 | | PA | 2-7 | 24-41-11 | D00274 | | 41 | | | | | GDX0001 | D.. | 2 | | ALL |
| 074 | 20 | | PA | 3-2 | 24-41-11 | D00268 | | 8 | | | | | GDX0001 | D.. | 2 | | ALL |
| 075 | 24 | | PK | 4-10 | 24-22-12 | D04028J | | 27 | | | | | D00268 | 21 | | | ALL |
| 076 | 20 | | PA | 4-10 | 24-22-12 | D04028J | | 28 | | | | | D00268 | 13 | | | ALL |
| 077 | 20 | | PA | 4-3 | 24-22-12 | D04028J | | 29 | | | | | D00274 | 14 | | | ALL |
| 078 | 20 | | PA | 3-5 | 24-22-12 | D00268 | | 14 | | | | | D00274 | 13 | | | ALL |
| 079 | 20 | | PA | 4-8 | 24-22-22 | D04026J | | 5 | | | | | D00268 | 17 | | | ALL |
| 080 | 20 | | PA | 4-1 | 24-22-22 | D04026J | | 6 | | | | | D00274 | 18 | | | ALL |
| 081 | 20 | | PA | 3-5 | 24-22-22 | D00268 | | 18 | | | | | D00274 | 17 | | | ALL |
| 082 | 24 | | PK | 3-10 | 24-41-11 | D04112J | | 53 | | | | | TB0024R | A002 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 20

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0026 | 286T0026 | | | P34-A2-APU PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | | |
| 083 | 24 | | PK | 3-10 | 24-41-11 | D04112J | | 54 | | | | | TB0024R | C002 | 2 | | ALL |
| 084 | 24 | | PK | 3-3 | 24-41-11 | D00274 | | 22 | | | | | TB0024R | C002 | 2 | | ALL |
| 085 | 24 | | PK | 3-5 | 24-41-11 | D00274 | | 21 | | | | | D00268 | | 22 | | ALL |
| 086 | 24 | | PK | 4-5 | 24-41-11 | D04028J | | 30 | | | | | B00129 | =1 | \$ | | ALL |
| 087 | 24 | | PK | 4-5 | 24-41-11 | D04028J | | 31 | | | | | B00129 | =2 | \$ | | ALL |
| 088 | 24 | | PK | 4-5 | 24-41-11 | D04028J | | 32 | | | | | B00130 | =1 | \$ | | ALL |
| 089 | 24 | | PK | 4-5 | 24-41-11 | D04028J | | 33 | | | | | B00130 | =2 | \$ | | ALL |
| 091 | 20 | | PA | 1-5 | 24-32-41 | D04112J | | 22 | | | | | D04028J | | 9 | | 150-199, 275-299 |
| 096 | 24 | | PK | 1-4 | 49-71-11 | D05340J | | 5 | | | | | D04028J | | 10 | | ALL |
| 097 | 22 | | PA | 3-10 | 49-61-11 | D04112J | | 49 | | | | | TB0024D | A013 | 2 | | ALL |
| 098 | 24 | | PK | 2-6 | 49-61-11 | TB0024D | | A013 | 2 | | | | TB0024D | A014 | 2 | | ALL |
| 100 | 24 | | PK | 3-10 | 24-27-41 | TB0024G | | 10 | 2 | | | | D04112J | | 31 | | ALL |
| 101 | 24 | | PK | 3-11 | 24-27-41 | TB0024G | | 10 | 2 | | | | D00268 | | 9 | | ALL |
| 102 | 24 | | PK | 4-4 | 24-27-41 | TB0024G | | 10 | 2 | | | | D05340J | | 2 | | ALL |
| 103 | 24 | | PK | 3-11 | 24-27-41 | TB0024G | | 11 | 2 | | | | D00268 | | 10 | | ALL |
| 104 | 24 | | PK | 3-10 | 24-27-41 | TB0024G | | 11 | 2 | | | | D04112J | | 32 | | ALL |
| 105 | 24 | | PK | 3-3 | 24-27-41 | TB0024G | | 11 | 2 | | | | D00274 | | 26 | | ALL |
| 106 | 24 | | PK | 4-3 | 24-27-41 | D04028J | | 4 | | | | | D00274 | | 25 | | 050-099, 162-199, 275-299 |
| 106 | 24 | | PK | 4-3 | 24-27-41 | D04028J | | 52 | | | | | D00274 | | 25 | | 150-157 |
| 107 | 24 | | PK | 4-1 | 28-25-21 | TB0024D | | C014 | 2 | | | | D04028J | | 11 | | ALL |
| 108 | 24 | | PK | 3-10 | 24-51-71 | D04112J | | 48 | | | | | TB0024F | A009 | 2 | | ALL |
| 109 | 24 | | PK | 4-10 | 24-51-71 | D04028J | | 25 | | | | | D00268 | | 24 | | ALL |
| 110 | 24 | | PK | 4-1 | 24-51-71 | D04028J | | 26 | | | | | TB0024F | A009 | 2 | | ALL |
| 111 | 24 | | PK | 4-6 | 24-51-71 | D04112J | | 47 | | | | | D00268 | | 23 | | ALL |
| 112 | 24 | | PK | 1-4 | 49-73-11 | D05340J | | 7 | | | | | D04028J | | 43 | | ALL |
| 113 | 24 | | PK | 1-4 | 24-34-11 | D05340J | | 9 | | | | | D04028J | | 42 | | ALL |
| 117 | 24 | | PK | 6-8 | 38-15-11 | C01354 | | 2 | D | | | | D04028J | | 8 | | ALL |
| 121 | 16 | | PA | 6-5 | 30-71-25 | D04026J | | 7 | | | | | C01167 | 2 | D | * | 050-099, 150-199 |
| 131 | 16 | | PA | 6-6 | 30-71-25 | D04028J | | 40 | FM | | | | C01167 | 2 | D | * | 050-099, 150-199 |
| 207B | 24 | | PL | N | 1-4 | 24-34-11 | | 11 | | | | | D04028J | | 53 | | ALL |
| 207R | 24 | | PL | N | 0-0 | 24-34-11 | | 10 | | | | | D04028J | | 54 | | ALL |
| 301B | 18 | | PC | F | 4-7 | 24-21-41 | | 2 | | | | | C00905 | T1 | H | | ALL |
| 301R | 18 | | PC | F | 0-0 | 24-21-41 | | 3 | | | | | C00905 | T2 | H | *2 | ALL |
| 301Y | 18 | | PC | F | 0-0 | 24-21-41 | | 4 | | | | | C00905 | T3 | H | *3 | ALL |
| 401B | 24 | | PN | B | 4-10 | 24-23-11 | | 37 | | | | | D00314 | | 1 | | ALL |
| 401G | 24 | | PN | B | 0-0 | 24-23-11 | | 38 | | | | | D00314 | | 2 | | ALL |
| 401R | 24 | | PN | B | 0-0 | 24-23-11 | | 39 | | | | | D00314 | | 3 | | ALL |
| 401Y | 24 | | PN | B | 0-0 | 24-23-11 | | 40 | | | | | D00314 | | 4 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0020
 Page 21
 Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0026 | 286T0026 | | | P34-A2-APU PWR DISTRIBUTION CONTROL (continued) | | | | | | | | | | | | |
| 402B | 24 | PN | C | 2-10 | 24-41-11 | D04112J | 41 | | | | D00376 | 4 | | ALL | | |
| 402G | 24 | PN | C | 0-0 | 24-41-11 | D04112J | 42 | | | | D00376 | 3 | | ALL | | |
| 402R | 24 | PN | C | 0-0 | 24-41-11 | D04112J | 43 | | | | D00376 | 2 | | ALL | | |
| 402Y | 24 | PN | C | 0-0 | 24-41-11 | D04112J | 44 | | | | D00376 | 1 | | ALL | | |
| 403B | 24 | PN | D | 4-7 | 24-23-12 | D00288 | 1 | | | | D04028J | 16 | | ALL | | |
| 403G | 24 | PN | D | 0-0 | 24-23-12 | D00288 | 2 | | | | D04028J | 17 | | ALL | | |
| 403R | 24 | PN | D | 0-0 | 24-23-12 | D00288 | 3 | | | | D04028J | 18 | | ALL | | |
| 403Y | 24 | PN | D | 0-0 | 24-23-12 | D00288 | 4 | | | | D04028J | 19 | | ALL | | |
| 404B | 24 | PN | E | 3-6 | 24-23-12 | D00290 | 1 | | | | D04028J | 20 | | ALL | | |
| 404G | 24 | PN | E | 0-0 | 24-23-12 | D00290 | 2 | | | | D04028J | 21 | | ALL | | |
| 404R | 24 | PN | E | 0-0 | 24-23-12 | D00290 | 3 | | | | D04028J | 22 | | ALL | | |
| 404Y | 24 | PN | E | 0-0 | 24-23-12 | D00290 | 4 | | | | D04028J | 23 | | ALL | | |
| W0028 | 286T0028 | | | P6-S2-MN PWR DISTR PNL | | | | | | | | | | | | |
| 001 | 22 | PQ | H | 6-0 | 28-22-21 | D04006J | 3 | | | | C01061 | 2 | D | ALL | | |
| 001Z | | | H | 0-0 | 28-22-21 | D04006J | DED | | | | C01061 | DED | | ALL | | |
| 002 | 24 | PK | | 6-0 | 29-21-31 | D04010J | 26 | | | | C01089 | 2 | D | ALL | | |
| 003 | 20 | PA | | 6-0 | 24-11-21 | D04008J | 5 | | | | C00805 | 1 | D | ALL | | |
| 004 | 18 | PA | | 6-0 | 24-11-21 | D04008J | 4 | | | | C00808 | 1 | D | ALL | | |
| 005 | 24 | PK | | 6-0 | 29-21-31 | D04010J | 25 | | | | C01100 | 2 | D | ALL | | |
| 007 | 18 | PA | | 3-0 | 24-33-11 | D04006J | 8 | | | | D00344 | A3 | | ALL | | |
| 011 | 24 | PK | | 3-0 | 24-33-11 | D04006J | 18 | | | | TB0014G | 6 | 2 | ALL | | |
| 012 | 24 | PK | | 4-0 | 24-33-11 | D00434 | A2 | | | | TB0014G | 6 | 2 | ALL | | |
| 013 | 12 | PA | | 6-0 | 32-35-11 | D04010J | 6 | | | | C04248 | 1 | D | ALL | | |
| 014 | 24 | PK | | 3-0 | 24-33-11 | D00438 | A2 | | | | TB0014G | 6 | 2 | ALL | | |
| 015 | 24 | PK | | 4-0 | 24-33-11 | D04006J | 21 | | | | K00106 | 14 | C | ALL | | |
| 016 | 24 | PK | | 6-0 | 24-33-11 | D04006J | 20 | | | | C04217 | 2 | D | ALL | | |
| 017 | 24 | PK | | 4-0 | 24-32-11 | D10180 | 11 | | | | K00108 | X1 | C | ALL | | |
| 018 | 24 | PK | | 6-0 | 24-32-11 | D04006J | 14 | | | | C00879 | 2 | D | ALL | | |
| 019 | 24 | PK | | 3-0 | 24-33-11 | D04006J | 19 | | | | TB0014F | A004 | 2 | ALL | | |
| 020 | 24 | PK | | 4-0 | 24-33-11 | D04006J | 22 | | | | D00356 | A3 | | ALL | | |
| 022 | 18 | PA | | 6-0 | 25-63-11 | C00748 | 1 | D | | | D04010J | 31 | DK | ALL | | |
| 023 | 18 | PA | | 6-0 | 24-11-11 | D04006J | 4 | | | | C00807 | 1 | D | ALL | | |
| 024 | 24 | PK | | 5-0 | 24-34-11 | D04008J | 27 | | | | TB0016X | B009 | BJ | ALL | | |
| 025 | 24 | PK | | 5-0 | 24-34-11 | D04008J | 26 | | | | TB0016X | C008 | BJ | ALL | | |
| 026 | 24 | PV | F | 6-0 | 24-34-11 | D04008J | 28 | | | | C04217 | 2 | D | ALL | | |
| 026Z | | | F | 0-0 | 24-34-11 | D04008J | DED | | | | C04217 | DED | | ALL | | |
| 033 | 24 | PK | | 5-0 | 24-28-11 | D04008J | 11 | | | | TB0016X | B008 | BJ | ALL | | |
| 034 | 18 | PA | | 6-0 | 28-41-12 | D04010J | 8 | | | | C01045 | 2 | D | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 22

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0028 | 286T0028 | | | P6-S2-MN PWR DISTR PNL (continued) | | | | | | | | | | | |
| 035 | 18 | | PA | | 6-0 | 28-26-11 | D04010J | | | 10 | C01044 | 2 | D | | ALL |
| 036 | 18 | | PA | | 6-0 | 28-21-11 | D04010J | | | 4 | C01043 | 2 | D | | ALL |
| 037 | 22 | | PQ | G | 6-0 | 32-44-11 | D04010J | | | 14 | C01179 | 1 | D | | ALL |
| 037Z | | | | G | 0-0 | 32-44-11 | D04010J | | DED | | C01179 | DED | | | ALL |
| 038 | 20 | | PQ | K | 6-0 | 24-11-11 | D04006J | | | 5 | C00804 | 1 | D | | ALL |
| 038Z | | | | K | 0-0 | 24-11-11 | D04006J | | DED | | C00804 | DED | | | ALL |
| 039 | 24 | | PK | | 6-0 | 24-31-11 | D04008J | | | 13 | C00827 | 1 | D | | ALL |
| 040 | 24 | | PK | | 3-0 | 24-31-11 | D04008J | | | 14 | D04126J | 3 | | | ALL |
| 041 | 20 | | PA | | 6-0 | 24-22-41 | D04006J | | | 11 | C00806 | 1 | D | | ALL |
| 042R | 20 | | PH | | 5-0 | 26-22-21 | D04006J | | | 28 | C00782 | 2 | D | | 275-299 |
| 043 | 20 | | PA | | 6-0 | 24-41-11 | D04006J | | | 24 | C00809 | 1 | D | | ALL |
| 045R | 20 | | PH | | 6-0 | 26-21-11 | D04006J | | | 29 | C00779 | 1 | D | | ALL |
| 046R | 20 | | PH | | 6-0 | 26-21-11 | D04008J | | | 29 | C00787 | 1 | D | | ALL |
| 047R | 20 | | PH | | 6-0 | 26-22-21 | D04010J | | | 29 | C00780 | 2 | D | | ALL |
| 049R | 20 | | PH | | 6-0 | 26-23-11 | D04006J | | | 31 | C00773 | 1 | D | | 050-099, 150-199 |
| 049R | 20 | | PH | | 6-0 | 26-23-12 | D04006J | | | 31 | C00773 | 1 | D | | 275-299 |
| 050 | 22 | | PA | | 6-0 | 28-25-21 | D04010J | | | 9 | C01063 | 2 | D | | 050-099 |
| 050 | 20 | | PA | | 6-0 | 28-25-21 | D04010J | | | 9 | C01063 | 2 | D | | 150-199, 275-299 |
| 051 | 22 | | PA | | 6-0 | 28-22-21 | D04008J | | | 3 | C01062 | 2 | D | | ALL |
| 054R | 20 | | PH | | 6-0 | 26-21-11 | D04006J | | | 30 | C00778 | 1 | D | | ALL |
| 055R | 20 | | PH | | 6-0 | 26-21-11 | D04008J | | | 30 | C00786 | 1 | D | | ALL |
| 056R | 20 | | PH | | 6-0 | 26-23-11 | D04008J | | | 31 | C00781 | 1 | D | | ALL |
| 057 | 24 | | PK | | 4-0 | 22-11-32 | D04010J | | | 20 | TB0016Y | C012 | BJ | | ALL |
| 058 | 24 | | PK | | 4-0 | 22-11-32 | D04010J | | | 19 | D00356 | X2 | | | ALL |
| 066 | 24 | | PK | | 4-0 | 24-31-11 | D04126J | | | 1 | K00104 | 13 | C | | ALL |
| 067 | 20 | | PA | | 4-0 | 24-31-11 | GD02414 | | D.. | 2 | K00104 | 14 | C | | ALL |
| 068 | 20 | | PA | | 3-0 | 24-32-11 | GD04500 | | D.. | 2 | D10180 | 7 | | | ALL |
| 069 | 20 | | PA | | 3-0 | 24-32-11 | GD04500 | | S.. | 2 | D10180 | 5 | | | ALL |
| 070 | 24 | | PK | | 5-0 | 24-32-11 | TB0016X | | C009 | BJ | D10180 | 6 | | | ALL |
| 071 | 24 | | PK | | 4-0 | 24-32-11 | D00344 | | D2 | | K00108 | X2 | C | | ALL |
| 072 | 24 | | PK | | 3-0 | 24-32-11 | D10180 | | | 8 | D00344 | D3 | | | 050-099, 275-299 |
| 072 | 24 | | PK | | 5-0 | 24-32-11 | TB0016X | | D009 | BJ | D00344 | D3 | | | 150-154 |
| 072 | 24 | | PK | | 5-0 | 24-32-11 | TB0016Y | | A013 | BJ | D00344 | D3 | | | 155-199 |
| 073 | 24 | | PK | | 3-0 | 24-32-11 | D04006J | | | 13 | K00108 | X1 | C | | ALL |
| 074 | 24 | | PK | | 5-0 | 24-32-11 | TB0016X | | D008 | BJ | D10180 | 4 | | | ALL |
| 075 | 20 | | PA | | 3-0 | 24-33-11 | GD02414 | | D.. | 2 | D00440 | 2 | | | ALL |
| 077 | 24 | | PK | | 5-0 | 24-33-11 | TB0016Y | | C002 | BJ | D00440 | 1 | | | ALL |
| 078 | 18 | | PA | | 5-0 | 24-51-31 | K00104 | | | 11 | C00880 | 2 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 23

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0028 | 286T0028 | | | P6-S2-MN PWR DISTR PNL (continued) | | | | | | | | | | | | |
| 079 | 18 | | PA | 4-0 | 24-51-31 | K00104 | 12 | C | * | D00344 | C2 | | | 050-099, 155-199, 277-299 | | |
| 079 | 18 | | PA | 4-0 | 24-51-31 | K00104 | 12 | C | | D00344 | C2 | | | 150-154, 275-276 | | |
| 080 | 24 | | PK | 5-0 | 24-33-11 | C00814 | 1 | D | | K00104 | X1 | C | | ALL | | |
| 081 | 24 | | PK | 2-0 | 24-33-11 | K00104 | X2 | C | | K00106 | 13 | C | | ALL | | |
| 083 | 24 | | PK | 5-0 | 24-33-11 | K00106 | X2 | C | | D00356 | A2 | | | ALL | | |
| 085 | 24 | | PK | 4-0 | 24-33-11 | D00434 | X1 | | | D04006J | 17 | | | ALL | | |
| 086 | 20 | | PA | 3-0 | 24-33-11 | D00434 | X2 | | | GD02414 | A.. | 2 | | ALL | | |
| 087 | 20 | | PA | 3-0 | 24-33-11 | D00434 | A3 | | | GD02414 | D.. | 2 | | ALL | | |
| 088 | 22 | | PA | 3-0 | 24-51-31 | D00328 | C3 | | | TB0014G | 11 | 2 | | ALL | | |
| 089 | 22 | | PA | 3-0 | 24-51-31 | D00328 | C1 | | | TB0014G | 11 | 2 | | ALL | | |
| 091 | 24 | | PK | 4-0 | 24-33-11 | D00438 | X1 | | | D04006J | 16 | | | ALL | | |
| 092 | 20 | | PA | 3-0 | 24-33-11 | D00438 | X2 | | | GD02414 | D.. | 2 | | ALL | | |
| 093 | 20 | | PA | 3-0 | 24-33-11 | D00438 | A3 | | | GD02414 | D.. | 2 | | ALL | | |
| 095 | 18 | | PQ | 5-0 | 24-51-31 | D00328 | A3 | | | TB0016F | A001 | 2 | | ALL | | |
| 095Z | | | | 0-0 | 24-51-31 | D00328 | DED | | | TB0016F | DED | | | ALL | | |
| 096 | 18 | | PA | 4-0 | 24-51-31 | D00328 | A1 | | | K00104 | 12 | C | * | 050-099, 155-199, 277-299 | | |
| 096 | 18 | | PA | 4-0 | 24-51-31 | D00328 | A1 | | | K00104 | 12 | C | | 150-154, 275-276 | | |
| 097 | 22 | | PQ | 5-0 | 24-51-31 | D00328 | B3 | | | TB0016Y | A002 | BJ | | ALL | | |
| 097Z | | | | 0-0 | 24-51-31 | D00328 | DED | | | TB0016Y | DED | | | ALL | | |
| 098 | 22 | | PA | 5-0 | 24-51-31 | D00328 | B1 | | | TB0016Y | A003 | BJ | | 050-099, 155-199, 277-299 | | |
| 098 | 22 | | PA | 5-0 | 24-51-31 | D00328 | B1 | | | TB0016Y | A013 | BJ | | 150-154, 275-276 | | |
| 099 | 20 | | PA | 3-0 | 24-51-31 | D00328 | X2 | | | GD02414 | D.. | 2 | | 050-099, 155-199, 277-299 | | |
| 099 | 18 | | PA | 3-0 | 24-51-31 | D00328 | X2 | | | GD02414 | D.. | 2 | | 150-154, 275-276 | | |
| 100 | 18 | | PA | 3-0 | 24-51-31 | D00328 | X1 | | | D13934 | B1 | | | ALL | | |
| 104 | 22 | | PA | 3-0 | 24-51-31 | D00356 | X1 | | | TB0014G | 9 | 2 | | ALL | | |
| 105 | 18 | | PA | 4-0 | 24-51-31 | D00344 | C1 | | | M00540 | A | C | | ALL | | |
| 108 | 20 | | PA | 4-0 | 24-51-31 | GD02414 | D.. | 2 | | K00108 | 12 | C | | ALL | | |
| 109 | 24 | | PK | 5-0 | 24-51-31 | D00344 | X1 | | | TB0016Y | A004 | BJ | | 050-099, 155-199, 277-299 | | |
| 109 | 24 | | PK | 5-0 | 24-51-31 | D00344 | X1 | | | TB0016Y | C013 | BJ | | 150-154, 275-276 | | |
| 110 | 20 | | PA | 3-0 | 24-51-31 | D00344 | X2 | | | GD02414 | D.. | 2 | | ALL | | |
| 111 | 18 | | PA | 2-0 | 34-21-21 | D00344 | C3 | | | D00348 | X1 | | | ALL | | |
| 112 | 18 | | PA | 3-0 | 34-21-21 | GD04500 | D.. | 2 | | D00348 | X2 | | | ALL | | |
| 114 | 16 | | PA | 6-0 | 34-21-11 | D04008J | 1 | | | C00614 | 1 | D | | ALL | | |
| 122 | 24 | | PK | 6-0 | 31-25-11 | D04010J | 22 | | | C00563 | 2 | D | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 24

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|-------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0028 | 286T0028 | | | P6-S2-MN PWR DISTR PNL (continued) | | | | | | | | | | | |
| 123 | 24 | | PK | | 6-0 | 31-25-11 | D04010J | 23 | | | C00576 | 2 | D | | ALL |
| 125 | 22 | | PA | | 6-0 | 23-22-11 | D04010J | 28 | | | C00538 | 2 | D | | ALL |
| 126 | 20 | | PA | | 6-0 | 28-21-13 | D04010J | 7 | | | C01046 | 2 | D | | ALL |
| 127 | 24 | | PK | | 5-0 | 24-33-11 | TB0016Y | C002 | BJ | | D00440 | 6 | | | ALL |
| 128 | 24 | | PK | | 3-0 | 24-33-11 | K00106 | X1 | C | | D00440 | 5 | | | ALL |
| 130 | 18 | | PA | | 3-0 | 24-33-11 | TB0014F | C003 | 2 | | D00344 | A2 | | | ALL |
| 135 | 18 | | PA | | 3-0 | 24-51-31 | D00328 | A2 | | | TB0014F | A008 | 2 | | ALL |
| 136 | 22 | | PA | | 1-0 | 24-51-31 | D00328 | B2 | | | D00328 | C2 | | | ALL |
| 137 | 24 | | PK | | 4-0 | 24-51-31 | D00328 | D3 | | | K00108 | 13 | C | | ALL |
| 138 | 24 | | PK | | 6-0 | 21-58-11 | D04010J | 16 | | | C00711 | 1 | D | | ALL |
| 141 | 24 | | PK | | 3-0 | 24-34-11 | D04008J | 16 | | | TB0014G | 5 | 2 | | ALL |
| 143 | 24 | | PK | | 3-0 | 24-34-11 | D04008J | 18 | | | D10408 | B2 | | | ALL |
| 144 | 24 | | PK | | 4-0 | 24-34-11 | K00108 | 11 | C | | D04008J | 19 | | | ALL |
| 145 | 24 | | PK | | 4-0 | 24-34-11 | D00344 | B3 | | | D04126J | 10 | | | ALL |
| 146 | 24 | | PK | | 8-0 | 24-34-11 | TB0016Z | 10 | BJ | | C04097 | 2 | D | | ALL |
| 148 | 24 | | PK | | 3-0 | 24-33-11 | TB0014G | 5 | 2 | | D04006J | 23 | | | ALL |
| 149 | 24 | | PK | | 5-0 | 24-32-11 | TB0016X | D009 | BJ | | D10180 | 8 | | | 150-154 |
| 149 | 24 | | PK | | 5-0 | 24-32-11 | TB0016Y | A013 | BJ | | D10180 | 8 | | | 155-199 |
| 150 | 24 | | PK | | 3-0 | 24-34-11 | D04126J | 7 | | | TB0014G | 5 | 2 | | ALL |
| 151 | 18 | | PQ | L | 5-0 | 25-29-11 | D00008 | = YEL | D | | TB0016F | A007 | 2 | | ALL |
| 151Z | | | | L | 0-0 | 25-29-11 | D00008 | DED | | | TB0016F | DED | | | ALL |
| 152 | 22 | | PQ | M | 5-0 | 25-29-11 | D00010 | Y | C | | TB0016F | C007 | 2 | | ALL |
| 152Z | | | | M | 0-0 | 25-29-11 | D00010 | DED | | | TB0016F | DED | | | ALL |
| 153 | 20 | | PQ | N | 4-0 | 25-29-11 | D00010 | X | C | | GD04500 | D.. | 2 | | ALL |
| 153Z | | | | N | 0-0 | 25-29-11 | D00010 | DED | | | GD04500 | DED | | | ALL |
| 154 | 18 | | PQ | P | 4-0 | 25-29-11 | D00008 | = WHT | | | | | 2 | | ALL |
| | | | | | | | | D | | | G~ | A.. | | | |
| | | | | | | | | | | | D~ | | | | |
| | | | | | | | | | | | 0~ | | | | |
| | | | | | | | | | | | 4~ | | | | |
| | | | | | | | | | | | 5~ | | | | |
| | | | | | | | | | | | 00 | | | | |
| 154Z | | | | P | 0-0 | 25-29-11 | D00008 | DED | | | GD04500 | DED | | | ALL |
| 155 | 18 | | PA | | 4-0 | 25-29-11 | D00008 | = GRN | D | | GD04500 | S.. | 2 | | ALL |
| 156 | 20 | | PA | | 4-0 | 25-29-11 | D00010 | W | C | | GD04500 | S.. | 2 | | ALL |
| 157 | 24 | | PV | R | 7-0 | 24-41-11 | D04006J | 25 | | | C00800 | 2 | D | | ALL |
| 157Z | | | | R | 0-0 | 24-41-11 | D04006J | DED | | | C00800 | DED | | | ALL |
| 158 | 24 | | PK | | 5-0 | 24-34-11 | D10406 | A2 | | | TB0016Z | 10 | BJ | | ALL |
| 159 | 24 | | PK | | 5-0 | 24-34-11 | D10406 | X1 | | | TB0016Z | 10 | BJ | | ALL |
| 160 | 24 | | PK | | 4-0 | 24-34-11 | D10406 | X2 | | | D04126J | 8 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0020
Page 25
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0028 | 286T0028 | | | P6-S2-MN PWR DISTR PNL (continued) | | | | | | | | | | | | | |
| 161 | 24 | | PK | 5-0 | 24-34-11 | D00344 | | B2 | | | | | TB0016Z | 10 | BJ | | ALL |
| 162 | 24 | | PK | 4-0 | 24-34-11 | D10410 | | X1 | | | | | TB0016Z | 10 | BJ | | ALL |
| 163 | 24 | | PK | 3-0 | 24-34-11 | D10408 | | B3 | | | | | D04126J | 9 | | | ALL |
| 164 | 24 | | PK | 3-3 | 24-34-11 | D10408 | | B1 | | | | | D10410 | B2 | | | ALL |
| 165 | 20 | | PA | 3-0 | 24-34-11 | D10408 | | A1 | | | | | GD02414 | D.. | 2 | | ALL |
| 166 | 24 | | PK | 5-0 | 24-34-11 | D10408 | | A2 | | | | | TB0016Y | A012 | BJ | | ALL |
| 167 | 24 | | PK | 3-0 | 24-34-11 | D10408 | | X1 | | | | | D10406 | A3 | | | ALL |
| 168 | 24 | | PK | 6-0 | 24-34-11 | D10408 | | X2 | | | | | TB0016Y | A012 | BJ | | ALL |
| 169 | 20 | | PA | 3-0 | 24-34-11 | D10410 | | B1 | | | | | GD02414 | D.. | 2 | | ALL |
| 170 | 20 | | PA | 3-0 | 24-34-11 | D10410 | | A1 | | | | | GD02414 | D.. | 2 | | ALL |
| 171 | 24 | | PK | 5-0 | 24-34-11 | D10410 | | A2 | | | | | TB0016Y | A012 | BJ | | ALL |
| 172 | 24 | | PK | 3-0 | 24-34-11 | D10410 | | X2 | | | | | D04006J | 26 | | | ALL |
| 173 | 24 | | PK | 3-0 | 24-33-11 | K00106 | | 11 | | C | | | TB0014G | 14 | 2 | | ALL |
| 174 | 24 | | PK | 3-0 | 24-33-11 | K00106 | | 12 | | C | | | TB0014G | 13 | 2 | | ALL |
| 175 | 24 | | PK | 3-0 | 24-33-11 | D04006J | | 12 | | | | | TB0014G | 13 | 2 | | ALL |
| 176 | 24 | | PK | 3-0 | 24-33-11 | D04006J | | 27 | | | | | TB0014G | 14 | 2 | | ALL |
| 177 | 24 | | PK | 3-0 | 24-51-31 | D00356 | | B2 | | | | | D04006J | 9 | | | ALL |
| 192 | 24 | | PK | 5-0 | 24-51-42 | D00344 | | D1 | | | | | TB0016Y | C005 | BJ | | ALL |
| 193 | 24 | | PK | 3-0 | 24-51-43 | D00328 | | D2 | | | | | TB0014F | C016 | 2 | | ALL |
| 194 | 24 | | PK | 4-0 | 24-51-31 | D00328 | | D1 | | | | | K00108 | 11 | C | | ALL |
| 195 | 24 | | PK | 3-0 | 24-51-31 | D00356 | | B1 | | | | | TB0014G | 9 | 2 | | ALL |
| 196 | 16 | | PA | 6-0 | 34-21-21 | D00348 | | A2 | | | | | C00620 | 1 | D | | 050-099 |
| 196 | 16 | | PA | 6-0 | 34-21-21 | C00620 | | 1 | | D | | | D00348 | A2 | | | 150-199, 275-299 |
| 197 | 16 | | PA | 6-0 | 34-21-31 | D04010J | | 1 | | | | | C00621 | 1 | D | | 050-099 |
| 197 | 16 | | PA | 6-0 | 34-21-31 | C00621 | | 1 | | D | | | D04010J | 1 | | | 150-199, 275-299 |
| 198 | 16 | | PA | 3-0 | 34-21-21 | D00348 | | A3 | | | | | D05828J | 1 | | | ALL |
| 199 | 22 | | PA | 7-0 | 24-25-11 | C00906 | | 2 | | D | | | D04008J | 17 | | | ALL |
| 201B | 24 | | PL | 2-0 | 24-34-11 | D04008J | | 20 | | | | | D04126J | 11 | | | ALL |
| 201R | 24 | | PL | 0-0 | 24-34-11 | D04008J | | 21 | | | | | D04126J | 12 | | | ALL |
| 202B | 24 | | PL | 4-0 | 24-34-11 | D04008J | | 22 | | | | | D04118J | 3 | | | ALL |
| 202R | 24 | | PL | 0-0 | 24-34-11 | D04008J | | 23 | | | | | D04118J | 4 | | | ALL |
| 203B | 24 | | PL | 4-0 | 24-34-11 | D04008J | | 24 | | | | | D04122J | 3 | | | ALL |
| 203R | 24 | | PL | 0-0 | 24-34-11 | D04008J | | 25 | | | | | D04122J | 4 | | | ALL |
| 501 | 20 | | PA | 6-0 | 25-33-11 | C00749 | | 1 | | D | | | D04006J | 1 | | | 050-099, 155-199, 277-299 |
| 603 | 18 | | PA | 3-0 | 24-51-31 | D13934 | | B2 | | | | | TB0014G | 12 | 2 | | ALL |
| 604 | 24 | | PK | 5-0 | 24-51-31 | D13934 | | A2 | | | | | TB0016Y | C003 | BJ | | 050-099, 155-199, 277-299 |
| 604 | 24 | | PK | 5-0 | 24-51-31 | D13934 | | A2 | | | | | TB0016Y | A005 | BJ | | 150-154, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0020

Page 26

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0028 | 286T0028 | | | P6-S2-MN PWR DISTR PNL (continued) | | | | | | | | | | | | |
| 605 | 24 | | PK | | 5-0 | 24-51-31 | D13934 | | A1 | | TB0016Y | A004 | BJ | | 050-099, 155-199, 277-299 | |
| 605 | 24 | | PK | | 5-0 | 24-51-31 | D13934 | | A1 | | TB0016Y | C013 | BJ | | 150-154, 275-276 | |
| 606 | 18 | | PA | | 3-0 | 24-51-31 | D13934 | | X1 | | TB0014G | 12 | 2 | | ALL | |
| 607 | 18 | | PA | | 3-0 | 24-51-31 | D13934 | | X2 | | GD02414 | D.. | 2 | | ALL | |
| 608 | 18 | | PA | | 3-0 | 24-51-31 | TB0014G | | 12 | 2 | M00540 | B | C | | ALL | |
| 609 | 22 | | PA | | 5-0 | 24-51-31 | D13936 | | X1 | | TB0016Y | A003 | BJ | | 050-099, 155-199, 277-299 | |
| 609 | 22 | | PA | | 5-0 | 24-51-31 | D13936 | | X1 | | TB0016Y | A013 | BJ | | 150-154, 275-276 | |
| 610 | 24 | | PK | | 5-0 | 24-51-31 | D13936 | | A1 | | TB0016Y | C003 | BJ | | 050-099, 155-199, 277-299 | |
| 610 | 24 | | PK | | 5-0 | 24-51-31 | D13936 | | A1 | | TB0016Y | A005 | BJ | | 150-154, 275-276 | |
| 611 | 24 | | PK | | 5-0 | 24-51-31 | D13936 | | A2 | | TB0016Y | A004 | BJ | | 050-099, 155-199, 277-299 | |
| 611 | 24 | | PK | | 5-0 | 24-51-31 | D13936 | | A2 | | TB0016Y | C013 | BJ | | 150-154, 275-276 | |
| 612 | 24 | | PK | | 4-0 | 24-51-31 | D04008J | | 9 | | TB0016Y | C003 | BJ | | 050-099, 155-199, 277-299 | |
| 612 | 24 | | PK | | 4-0 | 24-51-31 | D04008J | | 9 | | TB0016Y | A005 | BJ | | 150-154, 275-276 | |
| 613 | 20 | | PA | | 3-0 | 24-51-31 | D13936 | | X2 | | GD02414 | A.. | 2 | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0020
Page 27 End
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0030 | 286T0030 | | | P49-R1-APU AUX PANEL | | | | | | | | | | | | | |
| 001 | 20 | | PA | 8-0 | 36-11-41 | D05824P | | 8 | | | | | D03648 | A2 | | | ALL |
| 002 | 24 | | PK | 7-4 | 38-15-11 | D05874P | | 3 | | | | | D00692 | A3 | | | ALL |
| 003 | 24 | | PK | 2-0 | 38-15-11 | TB0300Y | A005 | BJ | | | | | D00692 | A1 | | | ALL |
| 004 | 24 | | PK | 2-0 | 38-15-11 | TB0300Y | A005 | BJ | | | | | D00692 | X1 | | | ALL |
| 005 | 20 | | PA | 2-1 | 38-15-11 | GDX0002 | D.. | 2 | | | | | D00692 | X2 | | | ALL |
| 006 | 12 | | PA | 7-2 | 38-32-11 | D05706P | | 4 | | | | | K00173 | A1 | E | | ALL |
| 007 | 12 | | PA | 7-3 | 38-32-11 | D05706P | | 5 | | | | | K00173 | B1 | E | | ALL |
| 008 | 12 | | PA | 7-3 | 38-32-11 | D05706P | | 6 | | | | | K00173 | C1 | E | | ALL |
| 009 | 22 | | PA | 3-9 | 38-32-11 | K00173 | X2 | C | | | | | TB0300G | 7 | 2 | | ALL |
| 010 | 18 | | PA | 7-5 | 38-15-11 | D05874P | | 13 | DL | | | | D00712 | C2 | | | ALL |
| 011 | 18 | | PA | 7-5 | 38-15-11 | D05874P | | 14 | DL | | | | D00712 | B2 | | | ALL |
| 012 | 18 | | PA | 7-5 | 38-15-11 | D05874P | | 15 | DL | | | | D00712 | A2 | | | ALL |
| 013 | 24 | | PK | 8-5 | 21-44-11 | D05672P | | 3 | | | | | TB0300Y | C002 | BJ | | ALL |
| 014 | 22 | | PA | 7-9 | 21-44-11 | D05672P | | 2 | | | | | D00694 | A2 | | | ALL |
| 015 | 24 | | PK | 7-9 | 21-44-11 | D05672P | | 1 | | | | | D00694 | B2 | | | ALL |
| 017 | 18 | | PA | 7-11 | 38-32-11 | D05874P | | 4 | DL | | | | TB0300G | 7 | 2 | | ALL |
| 018 | 18 | | PA | 8-5 | 38-32-11 | D05672P | | 9 | DL | | | | TB0300G | 7 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 018 | 18 | | PA | 8-5 | 38-32-15 | D05672P | | 9 | DL | | | | TB0300G | 7 | 2 | | 156-157, 166-199, 277-299 |
| 019 | 24 | | PK | 8-5 | 21-44-11 | D05672P | | 4 | | | | | TB0300Y | A002 | BJ | | ALL |
| 020 | 24 | | PK | 2-0 | 38-15-11 | TB0300Y | C005 | BJ | | | | | D00692 | A2 | | | ALL |
| 021 | 12 | | PA | 7-1 | 38-32-11 | D05706P | | 1 | | | | | K00173 | A2 | E | | ALL |
| 022 | 12 | | PA | 7-2 | 38-32-11 | D05706P | | 2 | | | | | K00173 | B2 | E | | ALL |
| 023 | 12 | | PA | 7-2 | 38-32-11 | D05706P | | 3 | | | | | K00173 | C2 | E | | ALL |
| 024 | 22 | | PA | 6-7 | 38-32-11 | D05672P | | 8 | | | | | K00173 | X1 | C | * | 050-099, 150-199, 277-299 |
| 024 | 22 | | PA | 6-7 | 38-32-11 | D05672P | | 8 | | | | | K00173 | X1 | C | | 275-276 |
| 025 | 22 | | PA | 2-2 | 38-15-11 | TB0300Y | C005 | BJ | | | | | D00712 | X1 | | | ALL |
| 026 | 22 | | PA | 7-5 | 38-15-11 | D05874P | | 2 | | | | | D00712 | X2 | | | ALL |
| 027 | 18 | | PA | 7-9 | 38-15-11 | D05824P | | 3 | | | | | D00712 | C1 | | | ALL |
| 028 | 18 | | PA | 7-9 | 38-15-11 | D05824P | | 2 | | | | | D00712 | B1 | | | ALL |
| 029 | 18 | | PA | 7-9 | 38-15-11 | D05824P | | 1 | | | | | D00712 | A1 | | | ALL |
| 030 | 24 | | PV | 7-9 | 21-44-11 | D05672P | | 5 | | | | | D00694 | X2 | | | ALL |
| 030Z | | | A | 0-0 | 21-44-11 | D05672P | DED | | | | | | D00694 | DED | | | ALL |
| 031 | 24 | | PK | 2-0 | 21-44-11 | TB0300Y | A002 | BJ | | | | | D00694 | B1 | | | ALL |
| 032 | 24 | | PK | 7-9 | 21-44-11 | D05672P | | 7 | | | | | D00694 | B3 | | | ALL |
| 033 | 24 | | PK | 8-5 | 21-44-11 | D05672P | | 6 | | | | | TB0300Y | A002 | BJ | | ALL |
| 034 | 24 | | PK | 7-11 | 36-11-41 | D05874P | | 5 | | | | | TB0300Z | 4 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 1

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|--|-----------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0030 | 286T0030 | | | P49-R1-APU AUX PANEL (continued) | | | | | | | | | | | | | | |
| 035 | 24 | | PK | | 6-3 | 36-11-41 | D05874P | | 6 | | | | D06394J | | 10 | | | 150-157 |
| 036 | 24 | | PK | | 7-8 | 36-11-41 | D05874P | | 8 | | | | D03648 | | X2 | | | ALL |
| 037 | 24 | | PK | | 2-8 | 36-11-41 | TB0300Z | | 4 | BJ | | | D03648 | | X1 | | | ALL |
| 038 | 24 | | PK | | 1-6 | 21-44-11 | D00694 | | A1 | | | | D10572 | | A2 | | | ALL |
| 039 | 22 | | PA | | 7-8 | 36-11-41 | D05874P | | 7 | | | | D03648 | | B2 | | | ALL |
| 040 | 24 | | PK | | 1-10 | 36-11-41 | D03652 | | 11 | | | | TB0300Z | | 4 | BJ | | ALL |
| 041 | 24 | | PK | | 1-10 | 36-11-41 | D03652 | | 6 | | | | TB0300Z | | 4 | BJ | | ALL |
| 042 | 24 | | PK | | 2-10 | 36-11-41 | D03650 | | X1 | | | | TB0300Z | | 4 | BJ | | ALL |
| 045 | 20 | | PA | | 3-0 | 36-11-41 | D06394J | | 5 | | | | D03648 | | A1 | | | ALL |
| 046 | 20 | | PA | | 3-0 | 36-11-41 | D06394J | | 6 | | | | D03648 | | A3 | | | ALL |
| 047 | 22 | | PA | | 1-7 | 36-11-41 | D03652 | | 1 | | | | D03648 | | B1 | | | ALL |
| 048 | 22 | | PA | | 1-6 | 36-11-41 | D03650 | | D2 | | | | D03648 | | B3 | | | ALL |
| 049 | 20 | | PA | | 1-11 | 36-11-41 | D03652 | | 13 | | | | GD0002 | | D.. | 2 | | ALL |
| 050 | 24 | | PK | | 2-6 | 36-11-41 | D03652 | | 10 | | | | D06394J | | 8 | | | ALL |
| 051 | 24 | | PK | | 2-6 | 36-11-41 | D06394J | | 7 | | | | D03652 | | 12 | | | ALL |
| 052 | 24 | | PK | | 3-2 | 36-11-41 | D06394J | | 9 | | | | D03650 | | X2 | | | ALL |
| 053 | 20 | | PA | | 2-6 | 36-11-41 | GD0002 | | D.. | 2 | | | D03650 | | D3 | | | ALL |
| 056 | 24 | | PK | | 7-11 | 38-15-11 | D05874P | | 1 | | | | TB0300Y | | C005 | BJ | | ALL |
| 057 | 18 | | PA | | 7-11 | 24-31-41 | D00402 | | A2 | | | | D04130P | | 1 | | | ALL |
| 058 | 18 | | PA | | 7-11 | 24-31-41 | D00402 | | B2 | | | | D04130P | | 2 | | | ALL |
| 062 | 24 | | PK | | 1-9 | 24-31-41 | D00402 | | X2 | | | | TB0300Y | | C009 | BJ | | ALL |
| 063 | 24 | | PK | | 3-5 | 24-31-41 | D00402 | | X1 | | | | C00820 | | 2 | D | | ALL |
| 064 | 18 | | PA | | 3-1 | 24-31-41 | D00402 | | C3 | | | | D06394J | | 2 | DL | | ALL |
| 065 | 18 | | PA | | 3-1 | 24-31-41 | D00402 | | B3 | | | | D06394J | | 3 | DL | | ALL |
| 066 | 18 | | PA | | 3-1 | 24-31-41 | D00402 | | A3 | | | | D06394J | | 4 | DL | | ALL |
| 075 | 18 | | PA | | 7-11 | 24-31-41 | D00402 | | C2 | | | | D04130P | | 3 | | | ALL |
| 083 | 24 | | PK | | 2-8 | 24-51-71 | TB0300X | | B011 | BJ | | | D03648 | | C2 | | | ALL |
| 084 | 24 | | PK | | 2-8 | 24-51-71 | TB0300X | | C011 | BJ | | | D03648 | | C1 | | | ALL |
| 091 | 24 | | PK | | 2-0 | 21-44-11 | D00694 | | X1 | | | | TB0300Y | | C002 | BJ | | ALL |
| 092 | 24 | | PK | | 1-10 | 21-44-11 | D10572 | | X1 | | | | TB0300Y | | C002 | BJ | | ALL |
| 093 | 24 | | PK | | 7-8 | 21-44-11 | D10572 | | X2 | | | | D05672P | | 12 | | | ALL |
| 094 | 20 | | PA | | 1-11 | 21-44-11 | D10572 | | A3 | | | | GD0002 | | D.. | 2 | | ALL |
| 126 | 22 | | PA | | 3-3 | 24-31-41 | D06394J | | 16 | | | | TB0300Y | | C009 | BJ | | ALL |
| 129 | 24 | | PK | | 2-10 | 31-31-22 | D03650 | | A3 | | | | TB0300F | | A014 | 2 | | ALL |
| 130 | 24 | | PK | | 1-10 | 31-31-22 | D03652 | | 9 | | | | TB0300F | | C014 | 2 | | ALL |
| 131 | 24 | | PK | | 2-10 | 36-11-41 | D03650 | | A2 | | | | TB0300Z | | 4 | BJ | | ALL |
| 133 | 20 | | PA | | 2-2 | 38-32-14 | D11932 | | X1 | | | | TB0294G | | 3 | 2 | | 050-099, 150-155, 157-165, 277 |
| 133 | 20 | | PA | | 4-0 | 38-32-14 | STA1362 | | CAP | Y | | | TB0294G | | 3 | 2 | | 156, 166 |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 2

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|---|-----------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0030 | 286T0030 | | | P49-R1-APU AUX PANEL (continued) | | | | | | | | | | | | | |
| 133 | 20 | | PA | 2-2 | 38-32-14 | D11932 | CAP | Y | | | | | TB0294G | 3 | 2 | | 167-199, 278-299 |
| 133 | 20 | | PA | 2-2 | 38-32-14 | D12392 | | X1 | | | | | TB0294G | 3 | 2 | | 275-276 |
| 134 | 20 | | PA | 3-0 | 38-32-14 | D11932 | | X2 | | | | | K00173 | X1 | C | * | 050-099, 150-155, 157-165, 277 |
| 134 | 20 | | PA | 4-0 | 38-32-14 | STA1362 | CAP | Y | | | | | K00173 | X1 | C | * | 156, 166 |
| 134 | 20 | | PA | 3-0 | 38-32-14 | D11932 | CAP | Y | | | | | K00173 | X1 | C | * | 167-199, 278-299 |
| 134 | 20 | | PA | 8-1 | 38-32-14 | D12392 | | X2 | | | | | D05706P | 7 | | | 275-276 |
| 135 | 18 | | PA | 8-1 | 38-32-14 | D11932 | | A1 | | | | | D05706P | 8 | | | 050-099, 150-155, 157-165, 277 |
| 135 | 18 | | PA | 8-0 | 38-32-14 | STA1362 | CAP | Y | | | | | D05706P | 8 | | | 156, 166 |
| 135 | 18 | | PA | 8-1 | 38-32-14 | D11932 | CAP | Y | | | | | D05706P | 8 | | | 167-199, 278-299 |
| 135 | 18 | | PA | 8-1 | 38-32-14 | D12392 | | A1 | | | | | D05706P | 8 | | | 275-276 |
| 136 | 18 | | PA | 2-2 | 38-32-14 | D11932 | | A2 | | | | | TB0294G | 3 | 2 | | 050-099, 150-155, 157-165, 277 |
| 136 | 18 | | PA | 4-0 | 38-32-14 | STA1362 | CAP | Y | | | | | TB0294G | 3 | 2 | | 156, 166 |
| 136 | 18 | | PA | 2-2 | 38-32-14 | D11932 | CAP | Y | | | | | TB0294G | 3 | 2 | | 167-199, 278-299 |
| 136 | 18 | | PA | 2-0 | 38-32-14 | D12392 | | A2 | | | | | GDX0002 | D.. | 2 | | 275-276 |
| 137 | 18 | | PA | 8-1 | 38-32-14 | D11932 | | A3 | | | | | D05706P | 7 | | | 050-099, 150-154 |
| 138 | 18 | | PA | 7-2 | 38-32-14 | D05874P | | 9 | DL | | | | TB0294G | 3 | 2 | | 050-099, 150-199, 277-299 |
| 141 | 22 | | PA | 7-7 | 38-32-14 | D05672P | | 13 | | | | | TB0294R | A004 | 2 | | 275-276 |
| 142 | 22 | | PA | 7-7 | 38-32-14 | D05672P | | 14 | | | | | TB0294R | C004 | 2 | | 275-276 |
| 143 | 22 | | PA | 7-7 | 38-32-14 | D05672P | | 15 | | | | | TB0294R | A005 | 2 | | 275-276 |
| 144 | 22 | | PA | 0-7 | 38-32-14 | TB0294G | | 3 | 2 | | | | TB0294R | C005 | 2 | | 275-276 |
| 145 | 20 | | PA | 2-0 | 38-32-15 | D12392 | | A2 | | | | | GDX0002 | D.. | 2 | | 156-157, 166-199, 277-299 |
| 146 | 20 | | PA | 7-8 | 38-32-15 | D12392 | | A1 | | | | | D05672P | 20 | | | 156-157, 166-199, 277-299 |
| 148 | 22 | | PA | 1-11 | 38-32-15 | D12392 | | X1 | | | | | TB0300G | 7 | 2 | | 156-157, 166-199, 277-299 |
| 149 | 20 | | PQ | FX | 1-6 | 38-32-15 | D12394 | A2 | | | | | GDX0002 | D.. | 2 | | 156-157, 166-199, 277-299 |
| 149Z | | | | FX | 0-0 | 38-32-15 | D12394 | DED | | | | | GDX0002 | DED | | | 156-157, 166-199, 277-299 |
| 150 | 20 | | PQ | FY | 8-5 | 38-32-15 | D12394 | A1 | | | | | D05672P | 18 | | | 156-157, 166-199, 277-299 |
| 150Z | | | | FY | 0-0 | 38-32-15 | D12394 | DED | | | | | D05672P | DED | | | 156-157, 166-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 3

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0030 | 286T0030 | | | P49-R1-APU AUX PANEL (continued) | | | | | | | | | | | |
| 151 | 20 | PQ | | GA | 8-5 | 38-32-15 | D12394 | | X2 | | D05672P | | 19 | | 156-157, 166-199, 277-299 |
| 151Z | | | | GA | 0-0 | 38-32-15 | D12394 | | DED | | D05672P | | DED | | 156-157, 166-199, 277-299 |
| 152 | 22 | PQ | | GE | 8-5 | 38-32-15 | D12394 | | X1 | | D05672P | | 16 | | 156-157, 166-199, 277-299 |
| 152Z | | | | GE | 0-0 | 38-32-15 | D12394 | | DED | | D05672P | | DED | | 156-157, 166-199, 277-299 |
| 154 | 20 | PA | | | 7-8 | 38-32-15 | D12392 | | X2 | | D05672P | | 21 | | 156-157, 166-199, 277-299 |
| 154 | 22 | PA | | | 2-11 | 38-32-14 | TB0294G | 3 | 2 | | TB0300G | 7 | 2 | | 275-276 |
| 201B | 24 | PL | F | | 7-10 | 21-51-12 | D05904P | 4 | | | D03652 | 7 | | | ALL |
| 201R | 24 | PL | F | | 0-0 | 21-51-12 | D05904P | 3 | | | D03652 | 8 | | | ALL |
| PA1 | | | | | 0-0 | 99-99-99 | D00712 | G2 | | | D00712 | G3 | | | ALL |
| W0031 | 286T0031 | | | P1, P3 AND P55 INSTRUMENT PANEL | | | | | | | | | | | |
| 001 | 22 | PA | | | 6-0 | 34-22-92 | D00717 | 40 | | | D04263P | 11 | | | ALL |
| 002 | 20 | PA | | | 5-0 | 34-22-92 | D00717 | 38 | | | GD00071 | A.. | 2 | | ALL |
| 003 | 20 | PA | | | 5-0 | 34-22-92 | D00717 | 20 | | | GD00077 | S.. | 2 | | ALL |
| 004 | 20 | PA | | | 5-0 | 34-22-92 | D00717 | | CAP | Y | GD00079 | D.. | 2 | | ALL |
| 005 | 24 | PK | | | 5-0 | 34-22-92 | D00717 | 8 | | | D05045P | 21 | | | ALL |
| 006 | 20 | PA | | | 5-0 | 34-22-92 | D05045P | 22 | | | GD00079 | D.. | 2 | | ALL |
| 007 | 24 | PK | | | 5-0 | 34-22-91 | D04263P | 8 | | | TB0243X | B003 | BJ | | 050-099 |
| 007 | 22 | PA | | | 5-0 | 34-22-91 | D04263P | 8 | | | TB0243X | B003 | BJ | | 150-199, 275-299 |
| 008 | 22 | PA | | | 8-0 | 33-16-15 | D05309P | 13 | | | TB0247Y | C004 | BJ | | ALL |
| 010 | 22 | PA | | | 8-0 | 33-16-15 | D05309P | 14 | | | TB0247Z | 10 | BJ | | ALL |
| 012 | 24 | PK | | | 7-0 | 34-22-27 | D05045P | 7 | | | D04391P | 4 | | | ALL |
| 013 | 24 | PK | | | 7-0 | 34-22-27 | D05045P | 8 | | | D04391P | 5 | | | ALL |
| 014 | 20 | PA | | | 5-0 | 34-22-27 | D05045P | 9 | | | GD00079 | D.. | 2 | | ALL |
| 015 | 24 | PK | | | 7-0 | 34-22-27 | D05045P | 10 | | | D04391P | 6 | | | ALL |
| 016 | 20 | PA | | | 5-0 | 34-22-27 | D05045P | 11 | | | GD00079 | D.. | 2 | | ALL |
| 018 | 24 | PK | | | 7-0 | 34-22-27 | D05045P | 16 | | | D04391P | 11 | | | ALL |
| 019 | 20 | PA | | | 5-0 | 34-22-27 | D05045P | 17 | | | GD00079 | D.. | 2 | | ALL |
| 021 | 20 | PA | | | 5-0 | 34-22-38 | D05045P | 28 | | | GD00079 | D.. | 2 | | ALL |
| 023 | 24 | PK | | | 13-0 | 34-22-26 | D04263P | 3 | | | D05813P | 6 | | | ALL |
| 024 | 24 | PK | | | 13-0 | 34-22-26 | D04263P | 4 | | | D05813P | 5 | | | ALL |
| 025 | 24 | PK | | | 10-0 | 34-22-38 | D04287P | 2 | | | D05045P | 29 | | | ALL |
| 027 | 24 | PK | | | 8-0 | 22-14-21 | D05555P | 18 | | | D00635 | 7 | | | ALL |
| 028 | 24 | PK | | | 8-0 | 22-14-21 | D04391P | 14 | | | D01365 | 7 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0030
Page 4
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0031 | 286T0031 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | | | |
| 029 | 24 | | PK | 8-0 | 22-14-21 | D04391P | | 15 | | | | | D01365 | | 5 | | | ALL |
| 030 | 20 | | PA | 7-0 | 22-14-21 | GD00079 | | S.. | 2 | | | | D01365 | | 12 | | | ALL |
| 031 | 20 | | PA | 7-0 | 22-14-21 | GD00073 | | S.. | 2 | | | | D00635 | | 11 | | | ALL |
| 033 | 24 | | PK | 8-0 | 22-14-21 | D05555P | | 19 | | | | | D00635 | | 5 | | | ALL |
| 034 | 24 | | PK | 8-0 | 22-14-21 | D04391P | | 13 | | | | | D01365 | | 9 | | | ALL |
| 036 | 20 | | PA | 7-0 | 34-13-21 | D00711 | | 10 | | | | | GD00079 | D.. | 2 | | | ALL |
| 037 | 20 | | PA | 6-0 | 34-13-21 | D00711 | | 7 | | | | | GD00077 | S.. | 2 | | | ALL |
| 038 | 20 | | PA | 6-0 | 34-13-21 | D00711 | | 4 | | | | | GD00071 | A.. | 2 | | | ALL |
| 039 | 22 | | PA | 8-0 | 34-13-21 | D00711 | | 3 | | | | | D04263P | | 13 | | | ALL |
| 044 | 20 | | PA | 5-0 | 34-13-21 | D00715 | | 10 | | | | | GD00079 | D.. | 2 | | | ALL |
| 045 | 20 | | PA | 5-0 | 34-13-21 | D00715 | | 7 | | | | | GD00077 | S.. | 2 | | | ALL |
| 046 | 20 | | PA | 5-0 | 34-13-21 | D00715 | | 4 | | | | | GD00071 | A.. | 2 | | | ALL |
| 047 | 22 | | PA | 6-0 | 34-13-21 | D00715 | | 3 | | | | | D04263P | | 15 | | | ALL |
| 048 | 24 | | PK | 12-0 | 34-13-21 | D00715 | | 12 | | | | | TB0241Y | A008 | BJ | | | ALL |
| 054 | 24 | | PK | 7-0 | 31-25-11 | D04263P | | 19 | | | | | D00719 | | 3 | | | 050-099 |
| 054 | 24 | | PK | 9-0 | 31-25-11 | D04263P | | 19 | | | | | D00719 | | 3 | | | 150-199, 275-299 |
| 055 | 20 | | PA | 6-0 | 31-25-11 | GD00077 | | S.. | 2 | | | | D00719 | | 7 | | | 050-099 |
| 055 | 20 | | PA | 6-0 | 31-25-11 | D00719 | | 7 | | | | | GD00077 | S.. | 2 | | | 150-199, 275-299 |
| 056 | 20 | | PA | 6-0 | 31-25-11 | GD00079 | | D.. | 2 | | | | D00719 | | 4 | | | 050-099 |
| 056 | 20 | | PA | 6-0 | 31-25-11 | D00719 | | 4 | | | | | GD00079 | D.. | 2 | | | 150-199, 275-299 |
| 057 | 20 | | PA | 6-0 | 31-25-11 | GD00079 | | D.. | 2 | | | | D00719 | | 9 | | | 050-099 |
| 057 | 20 | | PA | 6-0 | 31-25-11 | D00719 | | 9 | | | | | GD00079 | D.. | 2 | | | 150-199, 275-299 |
| 058 | 24 | | PK | 6-0 | 31-25-11 | TB0243X | | A004 | BJ | | | | D00719 | | 8 | | | 050-099 |
| 058 | 24 | | PK | 7-0 | 31-25-11 | D00719 | | 8 | | | | | TB0243X | A004 | BJ | | | 150-199, 275-299 |
| 059 | 22 | | PA | 8-0 | 22-14-21 | D01365 | | 1 | | | | | D04391P | | 17 | | | ALL |
| 060 | 22 | | PA | 8-0 | 22-14-21 | D00635 | | 1 | | | | | D05555P | | 20 | | | ALL |
| 064 | 24 | | PK | 10-0 | 34-22-28 | D00159 | | 27 | | | | | TB0241Y | A013 | BJ | | | ALL |
| 072 | 24 | | PK | 10-0 | 34-22-28 | D05813P | | 8 | | | | | D00159 | | 26 | | | ALL |
| 075 | 24 | | PK | 13-0 | 34-22-26 | D05813P | | 4 | | | | | D04263P | | 9 | | | ALL |
| 076 | 20 | | PA | 7-0 | 22-14-21 | D01365 | | 11 | | | | | GD00073 | D.. | 2 | | | ALL |
| 082 | 24 | | PK | 6-0 | 34-22-37 | D05045P | | 4 | | | | | D04391P | | 30 | | | ALL |
| 085 | 22 | | PQ | DJ | 6-0 | 33-16-15 | D00715 | | 11 | | | | TB0243Y | C016 | BJ | | | ALL |
| 085Z | | | | DJ | 0-0 | 33-16-15 | D00715 | | DED | | | | TB0243Y | | DED | | | ALL |
| 086 | 22 | | PQ | DK | 6-0 | 33-16-15 | D00715 | | 9 | | | | TB0247Z | | 9 | BJ | | ALL |
| 086Z | | | | DK | 0-0 | 33-16-15 | D00715 | | DED | | | | TB0247Z | | DED | | | ALL |
| 090 | 24 | | PK | | 7-0 | 34-21-31 | D05045P | | 27 | | | | D05555P | | 5 | | | ALL |
| 096 | 24 | | PK | | 7-0 | 31-51-21 | D05020J | | 7 | | | | D04321P | | 4 | | | ALL |
| 097 | 24 | | PK | | 11-0 | 31-51-21 | D05020J | | 8 | | | | TB0241Y | A007 | BJ | | | ALL |
| 101 | 24 | | PK | | 11-0 | 31-31-18 | D00224 | | 3 | | | | D04965P | | 1 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 5

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|--|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0031 | 286T0031 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | | | | |
| 102 | 24 | | PK | | 11-0 | 31-31-18 | D00224 | | 5 | | | | | D04965P | | 2 | | | ALL |
| 103 | 24 | | PK | | 11-0 | 31-31-18 | D00224 | | 7 | | | | | D04965P | | 3 | | | ALL |
| 104 | 24 | | PK | | 11-0 | 31-31-18 | D00224 | | 20 | | | | | D04965P | | 24 | | | ALL |
| 105 | 24 | | PK | | 11-0 | 31-31-18 | D00224 | | 2 | | | | | D04965P | | 25 | | | ALL |
| 106 | 24 | | PK | | 11-0 | 31-31-18 | D00224 | | 4 | | | | | D04965P | | 26 | | | ALL |
| 107 | 24 | | PK | | 11-0 | 31-31-18 | D00224 | | 6 | | | | | D04965P | | 40 | | | ALL |
| 108 | 24 | | PK | | 11-0 | 31-31-18 | D00224 | | 8 | | | | | D04965P | | 41 | | | ALL |
| 109 | 22 | | PA | | 11-0 | 31-31-18 | D00224 | | 21 | | | | | D04965P | | 52 | | | ALL |
| 130 | 20 | | PA | | 4-0 | 33-13-13 | D05045P | | 38 | | | | | SM00048 | | | W | | ALL |
| 131 | 20 | | PA | | 5-0 | 33-13-13 | D05045P | | 39 | | | | | GD00073 | A.. | 2 | | | ALL |
| 132 | 20 | | PA | | 4-0 | 33-13-13 | D00715 | | 1 | | | | | SM00048 | | | W | | ALL |
| 133 | 20 | | PA | | 5-0 | 33-13-13 | D00715 | | 2 | | | | | GD00073 | A.. | 2 | | | ALL |
| 134 | 20 | | PA | | 4-0 | 33-13-13 | D00717 | | 42 | | | | | SM00048 | | | W | | ALL |
| 135 | 20 | | PA | | 4-0 | 33-13-13 | D00717 | | 43 | | | | | GD00073 | A.. | 2 | | | ALL |
| 136 | 20 | | PA | | 5-0 | 33-13-13 | D00719 | | 1 | | | | | SM00048 | | | W | | ALL |
| 137 | 20 | | PA | | 6-0 | 33-13-13 | D00719 | | 2 | | | | | GD00073 | A.. | 2 | | | ALL |
| 138 | 20 | | PA | | 5-0 | 33-13-13 | D01365 | | 3 | | | | | SM00049 | | | W | | ALL |
| 139 | 20 | | PA | | 6-0 | 33-13-13 | D01365 | | 13 | | | | | GD03096 | A.. | 2 | | | ALL |
| 140 | 20 | | PA | | 6-0 | 33-13-13 | D00238 | | 1 | | | | | SM00049 | | | W | | 050-099, 151 |
| 140 | 20 | | PA | | 5-0 | 33-13-13 | SPZ0001 | | | S | | | | SM00049 | | | W | | 150, 152-199, 275-299 |
| 141 | 20 | | PA | | 6-0 | 33-13-13 | D00238 | | 2 | | | | | GD03096 | A.. | 2 | | | ALL |
| 144 | 20 | | PA | | 6-0 | 33-13-13 | D00711 | | 1 | | | | | SM00049 | | | W | | 050-099, 150-199, 275-278 |
| 145 | 20 | | PA | | 6-0 | 33-13-13 | D00711 | | 2 | | | | | GD03096 | A.. | 2 | | | 050-099, 150-199, 275-278 |
| 150 | 20 | | PA | | 1-11 | 33-13-13 | TB0247X | | | B005 | BJ | | | SM00048 | | | W | | ALL |
| 151 | 20 | | PA | | 1-11 | 33-13-13 | TB0247Y | | | A001 | BJ | | | SM00049 | | | W | | ALL |
| 152 | 22 | | PA | | 5-0 | 33-13-13 | D05399P | | 13 | | | | | TB0247X | C006 | | BJ | | ALL |
| 156 | 22 | | PA | | 4-0 | 34-13-21 | D05045P | | 26 | | | | | SM00037 | | | W | | 050-099 |
| 156 | 22 | | PA | | 5-0 | 34-13-21 | D05045P | | 26 | | | | | SM00037 | | | W | | 150-199, 275-299 |
| 157 | 20 | | PA | | 5-0 | 34-12-62 | D05045P | | 23 | | | | | GD00077 | D.. | 2 | | | ALL |
| 159 | 20 | | PA | | 5-0 | 34-12-62 | D05045P | | 25 | | | | | GD00077 | D.. | 2 | | | ALL |
| 165 | 22 | | PA | | 4-0 | 34-13-21 | D00715 | | 8 | | | | | SM00037 | | | W | | ALL |
| 166 | 22 | | PA | | 6-0 | 34-13-21 | D00711 | | 8 | | | | | SM00037 | | | W | | ALL |
| 167 | 20 | | PA | | 5-0 | 34-13-21 | D00715 | | 38 | | | | | GD00077 | D.. | 2 | | | ALL |
| 168 | 24 | | PK | | 12-0 | 22-41-13 | D04287P | | 1 | | | | | D04391P | | 35 | | | ALL |
| 169 | 24 | | PK | | 7-0 | 22-41-13 | D05045P | | 32 | | | | | D04391P | | 36 | | | ALL |
| 170 | 24 | | PK | | 7-0 | 22-41-13 | D05045P | | 31 | | | | | D04391P | | 37 | | | ALL |
| 171 | 20 | | PA | | 5-0 | 22-41-13 | D05045P | | 33 | | | | | GD00077 | D.. | 2 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0030
Page 6
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0031 | 286T0031 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 172 | 22 | | PA | | 7-0 | 34-22-26 | D05045P | | 34 | | D04391P | | 16 | | ALL |
| 173 | 20 | | PA | | 5-0 | 34-22-26 | D05045P | | 35 | | GD00079 | D.. | 2 | | ALL |
| 176 | 24 | | PK | | 6-0 | 32-42-11 | D05045P | | 36 | | D04965P | | 27 | | ALL |
| 177 | 20 | | PA | | 5-0 | 32-42-11 | D05045P | | 37 | | GD00077 | D.. | 2 | | ALL |
| 178 | 22 | | PA | | 6-0 | 34-12-62 | D05045P | | 3 | | D04965P | | 28 | | ALL |
| 180 | 22 | | PA | | 6-0 | 34-22-27 | D04391P | | 31 | | D05045P | | 55 | | ALL |
| 188 | 24 | | PK | | 8-0 | 31-31-19 | D00232 | | 13 | | D04965P | | 46 | | 050-099 |
| 188 | 24 | | PK | | 9-0 | 31-31-19 | D04965P | | 46 | | D00232 | | 13 | | 150-199, 275-299 |
| 189 | 24 | | PK | | 8-0 | 31-31-19 | D00232 | | 14 | | D04965P | | 47 | | 050-099 |
| 189 | 24 | | PK | | 9-0 | 31-31-19 | D04965P | | 47 | | D00232 | | 14 | | 150-199, 275-299 |
| 202B | 24 | | PW | IB | 6-0 | 34-22-92 | D00717 | | 48 | | D04391P | | 2 | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-22-92 | D00717 | | 47 | | D04391P | | 1 | | ALL |
| 202Z | | | | IB | 0-0 | 34-22-92 | D00717 | DED | | | D04391P | | 3 | | ALL |
| 204B | 22 | | PR | ID | 6-0 | 34-12-11 | D00715 | | 28 | | D05555P | | 22 | | ALL |
| 204R | 22 | | PR | ID | 0-0 | 34-12-11 | D00715 | | 27 | | D05555P | | 21 | | ALL |
| 204Z | | | | ID | 0-0 | 34-12-11 | D00715 | DED | | | D05555P | DED | | | ALL |
| 209B | 24 | | PW | II | 12-0 | 34-22-92 | D00717 | | 45 | | TB0241Y | C008 | BJ | | ALL |
| 209R | 24 | | PW | II | 0-0 | 34-22-92 | D00717 | | 26 | | TB0241Y | C007 | BJ | | ALL |
| 209Z | | | | II | 0-0 | 34-22-92 | D00717 | DED | | | TB0241X | C006 | BJ | | ALL |
| 224B | 22 | | PB | IX | 6-0 | 34-12-21 | D00715 | | 23 | | D04965P | | 5 | | ALL |
| 224R | 22 | | PB | IX | 0-0 | 34-12-21 | D00715 | | 22 | | D04965P | | 4 | | ALL |
| 225B | 24 | | PW | IY | 6-0 | 34-13-21 | D00711 | | 31 | | SM00020 | | W | | ALL |
| 225R | 24 | | PW | IY | 0-0 | 34-13-21 | D00711 | | 30 | | SM00019 | | W | | ALL |
| 225Z | | | | IY | 0-0 | 34-13-21 | D00711 | DED | | | SM00019 | REF | | FF | ALL |
| 227B | 24 | | PW | JB | 4-0 | 34-13-21 | D04965P | | 10 | | SM00020 | | W | | ALL |
| 227R | 24 | | PW | JB | 0-0 | 34-13-21 | D04965P | | 9 | | SM00019 | | W | | ALL |
| 227Z | | | | JB | 0-0 | 34-13-21 | D04965P | | 11 | | SM00019 | REF | | FF | ALL |
| 228B | 24 | | PW | JC | 4-0 | 34-13-21 | D00715 | | 31 | | SM00020 | | W | | ALL |
| 228R | 24 | | PW | JC | 0-0 | 34-13-21 | D00715 | | 30 | | SM00019 | | W | | ALL |
| 228Z | | | | JC | 0-0 | 34-13-21 | D00715 | DED | | | SM00019 | REF | | FF | ALL |
| 229B | 24 | | PW | JD | 5-0 | 22-14-21 | D04965P | | 34 | | TB0243Y | A002 | BJ | | ALL |
| 229R | 24 | | PW | JD | 0-0 | 22-14-21 | D04965P | | 33 | | TB0243Y | A001 | BJ | | ALL |
| 229Z | | | | JD | 0-0 | 22-14-21 | D04965P | | 38 | | TB0243Y | REF | | JD | ALL |
| 230 | 20 | | UA | | 1-6 | 22-14-21 | D00477 | | | JE | GD00311 | S.. | 2 | | ALL |
| 230B | 24 | | PW | JE | 8-0 | 22-14-21 | D00477 | | 27 | | TB0243Y | A002 | BJ | | ALL |
| 230R | 24 | | PW | JE | 0-0 | 22-14-21 | D00477 | | 26 | | TB0243Y | A001 | BJ | | ALL |
| 230Z | | | | JE | 0-0 | 22-14-21 | D00477 | | | JE | TB0243Y | REF | | JD | ALL |
| 231B | 24 | | PW | JF | 7-0 | 22-14-21 | D00711 | | 25 | | TB0243Y | A002 | BJ | | ALL |
| 231R | 24 | | PW | JF | 0-0 | 22-14-21 | D00711 | | 24 | | TB0243Y | A001 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 7

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|---------|------|--------|-------------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0031 | 286T0031 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | |
| 231Z | | | | JF | 0-0 | 22-14-21 | D00711 | | DED | | TB0243Y | | REF | | JD | ALL |
| 232B | 24 | PW | | JG | 8-0 | 34-61-24 | D00719 | | 23 | | D04965P | | 13 | | | 050-099 |
| 232B | 24 | PW | | JG | 7-0 | 34-61-24 | D00719 | | 23 | | D04965P | | 13 | | | 150-199, 275-299 |
| 232R | 24 | PW | | JG | 0-0 | 34-61-24 | D00719 | | 24 | | D04965P | | 12 | | | ALL |
| 232Z | | | | JG | 0-0 | 34-61-24 | D00719 | | DED | | D04965P | | 14 | | | ALL |
| 241B | 24 | PW | | JP | 7-0 | 34-13-21 | D00711 | | 27 | | TB0243Y | | A006 | BJ | | 050-099 |
| 241B | 24 | PW | | JP | 8-0 | 34-13-21 | D00711 | | 27 | | TB0243Y | | C006 | BJ | | 150-156, 162-199 |
| 241B | 24 | PW | | JP | 8-0 | 34-13-21 | D00711 | | 27 | | TB0243Y | | A006 | BJ | | 157, 275-299 |
| 241R | 24 | PW | | JP | 0-0 | 34-13-21 | D00711 | | 26 | | TB0243Y | | A005 | BJ | | ALL |
| 241Z | | | | JP | 0-0 | 34-13-21 | D00711 | | DED | | TB0243Y | | REF | | FP | ALL |
| 242B | 24 | PW | | JQ | 6-0 | 34-13-21 | D00715 | | 34 | | TB0243Y | | A006 | BJ | | ALL |
| 242R | 24 | PW | | JQ | 0-0 | 34-13-21 | D00715 | | 33 | | TB0243Y | | A005 | BJ | | ALL |
| 242Z | | | | JQ | 0-0 | 34-13-21 | D00715 | | DED | | TB0243Y | | REF | | FP | ALL |
| 249B | 24 | PW | | JX | 5-0 | 34-22-91 | D04965P | | 54 | | TB0243Y | | C006 | BJ | | ALL |
| 249R | 24 | PW | | JX | 0-0 | 34-22-91 | D04965P | | 53 | | TB0243Y | | C005 | BJ | | ALL |
| 249Z | | | | JX | 0-0 | 34-22-91 | D04965P | | 55 | | TB0243X | | D004 | BJ | | ALL |
| 256B | 24 | PW | | KF | 10-0 | 34-45-14 | D04893P | | 3 | | D05309P | | CAP | Y | | 153-154 |
| 256R | 24 | PW | | KF | 0-0 | 34-45-14 | D04893P | | 2 | | D05309P | | CAP | Y | | 153-154 |
| 256Z | | | | KF | 0-0 | 34-45-14 | D04893P | | 4 | | D05309P | | DED | | | 153-154 |
| 259B | 24 | PW | | KI | 6-0 | 34-45-14 | D04893P | | 18 | | D00717 | | 44 | | | ALL |
| 259R | 24 | PW | | KI | 0-0 | 34-45-14 | D04893P | | 17 | | D00717 | | 25 | | | ALL |
| 259Z | | | | KI | 0-0 | 34-45-14 | D04893P | | 19 | | D00717 | | DED | | | ALL |
| 301B | 24 | PM | | MA | 6-0 | 34-12-21 | D04965P | | 7 | | D00715 | | 20 | | | ALL |
| 301R | 24 | PM | | MA | 0-0 | 34-12-21 | D04965P | | 6 | | D00715 | | 19 | | | ALL |
| 301Y | 24 | PM | | MA | 0-0 | 34-12-21 | D04965P | | 8 | | D00715 | | 21 | | | ALL |
| 302 | 20 | UA | | | 6-0 | 31-25-11 | GD00077 | | S.. | 2 | | | | | MB | 050-099 |
| 302 | 20 | UA | | | 7-0 | 31-25-11 | D00719 | | | | MB | GD00077 | S.. | 2 | | 150-199 |
| 302 | 20 | UA | | | 7-0 | 31-25-11 | D00719 | | REF | | MB | GD00077 | S.. | 2 | | 275-299 |
| 302B | 24 | PX | | MB | 7-0 | 31-25-11 | D05020J | | 2 | | D00719 | | 14 | | | 050-099 |
| 302B | 24 | PX | | MB | 7-0 | 31-25-11 | D00719 | | 14 | | D05020J | | 2 | | | 150-199, 275-299 |
| 302R | 24 | PX | | MB | 0-0 | 31-25-11 | D05020J | | 1 | | D00719 | | 13 | | | 050-099 |
| 302R | 24 | PX | | MB | 0-0 | 31-25-11 | D00719 | | 13 | | D05020J | | 1 | | | 150-199, 275-299 |
| 302Y | 24 | PX | | MB | 0-0 | 31-25-11 | D05020J | | 3 | | D00719 | | 15 | | | 050-099 |
| 302Y | 24 | PX | | MB | 0-0 | 31-25-11 | D00719 | | 15 | | D05020J | | 3 | | | 150-199, 275-299 |
| 302Z | | | | MB | 0-0 | 31-25-11 | D05020J | | 14 | | D00719 | | | | MB | 050-099 |
| 302Z | | | | MB | 0-0 | 31-25-11 | D00719 | | | | MB | D05020J | | 14 | | 150-199 |
| 302Z | | | | MB | 0-0 | 31-25-11 | D00719 | | REF | | MB | D05020J | | 14 | | 275-299 |
| 308B | 24 | PM | | MH | 6-0 | 34-12-11 | D00715 | | 25 | | D04391P | | 33 | | | ALL |
| 308R | 24 | PM | | MH | 0-0 | 34-12-11 | D00715 | | 24 | | D04391P | | 32 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 8

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|---------|-------|-------------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0031 | 286T0031 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 308Y | 24 | PM | MH | | 0-0 | 34-12-11 | D00715 | | 26 | | D04391P | | 34 | | ALL |
| 350B | 24 | PM | NY | | 4-0 | 31-41-14 | D05117P | | 6 | | D05113P | | 12 | | ALL |
| 350R | 24 | PM | NY | | 0-0 | 31-41-14 | D05117P | | 5 | | D05113P | | 11 | | ALL |
| 350Y | 24 | PM | NY | | 0-0 | 31-41-14 | D05117P | | 7 | | D05113P | | 13 | | ALL |
| 351B | 24 | PX | OA | | 9-0 | 23-51-12 | D00159 | | 25 | | D05417P | | 18 | | ALL |
| 351R | 24 | PX | OA | | 0-0 | 23-51-12 | D00159 | | 24 | | D05417P | | 17 | | ALL |
| 351Y | 24 | PX | OA | | 0-0 | 23-51-12 | D00159 | | 12 | | D05417P | | 19 | | ALL |
| 351Z | | | OA | | 0-0 | 23-51-12 | D00159 | | DED | | D05417P | | 20 | | ALL |
| 352B | 24 | PM | OB | | 5-0 | 33-13-17 | D05399P | | 15 | | TB0247X | B007 | BJ | | ALL |
| 352R | 24 | PM | OB | | 0-0 | 33-13-17 | D05399P | | 16 | | TB0247X | A008 | BJ | | ALL |
| 352Y | 24 | PM | OB | | 0-0 | 33-13-17 | D05399P | | 17 | | TB0247X | B008 | BJ | | ALL |
| 501B | 24 | PW | UA | | 4-0 | 31-41-12 | D05117P | | 3 | | D05113P | | 3 | | ALL |
| 501R | 24 | PW | UA | | 0-0 | 31-41-12 | D05117P | | 2 | | D05113P | | 2 | | ALL |
| 501Z | | | UA | | 0-0 | 31-41-12 | D05117P | | 4 | | D05113P | | 4 | | ALL |
| 502B | 24 | PL | UB | | 5-0 | 31-41-14 | TB0241Y | A004 | BJ | | D05113P | | 6 | | ALL |
| 502R | 24 | PL | UB | | 0-0 | 31-41-14 | TB0241Y | A003 | BJ | | D05113P | | 5 | | ALL |
| 504B | 24 | PL | UD | | 5-0 | 31-41-14 | TB0241X | A005 | BJ | | D05113P | | 8 | | ALL |
| 504R | 24 | PL | UD | | 0-0 | 31-41-14 | TB0241X | A006 | BJ | | D05113P | | 7 | | ALL |
| 505B | 24 | PL | UE | | 5-0 | 31-41-14 | TB0241X | B005 | BJ | | D05113P | | 10 | | ALL |
| 505R | 24 | PL | UE | | 0-0 | 31-41-14 | TB0241X | B006 | BJ | | D05113P | | 9 | | ALL |
| 509B | 24 | PW | UI | | 11-0 | 73-21-14 | D10124 | | 16 | | D06180P | | 26 | | ALL |
| 509R | 24 | PW | UI | | 0-0 | 73-21-14 | D10124 | | 15 | | D06180P | | 27 | | ALL |
| 509Z | | | UI | | 0-0 | 73-21-14 | D10124 | | | UI | D06180P | | 31 | | 050-099 |
| 509Z | | | UI | | 0-0 | 73-21-14 | D10124 | REF | | UI | D06180P | | 31 | | 150-199, 275-299 |
| 510B | 24 | PW | UJ | | 11-0 | 73-21-14 | D10124 | | 24 | | D06178P | | 10 | | ALL |
| 510R | 24 | PW | UJ | | 0-0 | 73-21-14 | D10124 | | 23 | | D06178P | | 9 | | ALL |
| 510Z | | | UJ | | 0-0 | 73-21-14 | D10124 | | | UI | D06178P | | 18 | | 050-099 |
| 510Z | | | UJ | | 0-0 | 73-21-14 | D10124 | REF | | UI | D06178P | | 18 | | 150-199, 275-299 |
| 512 | 20 | UA | | | 1-6 | 22-12-21 | D00477 | | | UL | GD00311 | S.. | 2 | | ALL |
| 512B | 24 | PW | UL | | 9-0 | 22-12-21 | D00477 | | 21 | | D05423P | | 5 | | ALL |
| 512R | 24 | PW | UL | | 0-0 | 22-12-21 | D00477 | | 20 | | D05423P | | 4 | | ALL |
| 512Z | | | UL | | 0-0 | 22-12-21 | D00477 | | | UL | D05423P | | 6 | | ALL |
| 513 | 20 | UA | | | 1-6 | 22-13-21 | D00477 | | | UM | GD00311 | S.. | 2 | | ALL |
| 513B | 24 | PW | UM | | 9-0 | 22-13-21 | D00477 | | 29 | | D05423P | | 8 | | ALL |
| 513R | 24 | PW | UM | | 0-0 | 22-13-21 | D00477 | | 28 | | D05423P | | 7 | | ALL |
| 513Z | | | UM | | 0-0 | 22-13-21 | D00477 | | | UM | D05423P | | 9 | | ALL |
| 514 | 20 | UA | | | 1-6 | 22-14-21 | D00477 | | | UN | GD00311 | S.. | 2 | | ALL |
| 514B | 24 | PW | UN | | 9-0 | 22-14-21 | D00477 | | 23 | | D05423P | | 11 | | ALL |
| 514R | 24 | PW | UN | | 0-0 | 22-14-21 | D00477 | | 24 | | D05423P | | 10 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 9

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0031 | 286T0031 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 514Z | | | UN | 0-0 | 22-14-21 | D00477 | | | UN | D05423P | 12 | | | ALL | |
| 516B | 24 | PW | UP | 9-0 | 34-55-21 | D00159 | | 29 | | D05417P | 3 | | | ALL | |
| 516R | 24 | PW | UP | 0-0 | 34-55-21 | D00159 | | 16 | | D05417P | 2 | | | ALL | |
| 516Z | | | UP | 0-0 | 34-55-21 | D00159 | | 28 | | D05417P | 4 | | | ALL | |
| 517B | 24 | PW | UQ | 9-0 | 34-51-21 | D00159 | | 21 | | D05417P | 7 | | | ALL | |
| 517R | 24 | PW | UQ | 0-0 | 34-51-21 | D00159 | | 8 | | D05417P | 6 | | | ALL | |
| 517Z | | | UQ | 0-0 | 34-51-21 | D00159 | | 20 | | D05417P | 8 | | | ALL | |
| 518B | 24 | PW | UR | 9-0 | 34-51-21 | D00159 | | 31 | | D05417P | 10 | | | ALL | |
| 518R | 24 | PW | UR | 0-0 | 34-51-21 | D00159 | | 18 | | D05417P | 9 | | | ALL | |
| 518Z | | | UR | 0-0 | 34-51-21 | D00159 | | 30 | | D05417P | 11 | | | ALL | |
| 519B | 24 | PW | US | 9-0 | 34-51-21 | D00159 | | 22 | | D05417P | 15 | | | ALL | |
| 519R | 24 | PW | US | 0-0 | 34-51-21 | D00159 | | 10 | | D05417P | 14 | | | ALL | |
| 519Z | | | US | 0-0 | 34-51-21 | D00159 | | 23 | | D05417P | 16 | | | ALL | |
| 520B | 22 | PB | UT | 9-0 | 34-51-21 | D00159 | | 2 | | D05417P | 13 | | | ALL | |
| 520R | 22 | PB | UT | 0-0 | 34-51-21 | D00159 | | 1 | | D05417P | 12 | | | ALL | |
| 521B | 20 | PR | UU | 5-0 | 34-12-21 | D04893P | | 40 | | TB0243X | A008 | BJ | | ALL | |
| 521R | 20 | PR | UU | 0-0 | 34-12-21 | D04893P | | 39 | | TB0243X | A007 | BJ | | ALL | |
| 521Z | | | UU | 0-0 | 34-12-21 | D04893P | | 41 | | TB0243X | B008 | BJ | | ALL | |
| 522B | 24 | PW | UV | 13-0 | 34-13-11 | D04893P | | 45 | | TB0241Y | C010 | BJ | | ALL | |
| 522R | 24 | PW | UV | 0-0 | 34-13-11 | D04893P | | 44 | | TB0241Y | C009 | BJ | | ALL | |
| 522Z | | | UV | 0-0 | 34-13-11 | D04893P | | 46 | | TB0241X | C011 | BJ | | ALL | |
| 523B | 24 | PW | UW | 13-0 | 34-22-81 | D04893P | | 30 | | TB0241X | D012 | BJ | | ALL | |
| 523R | 24 | PW | UW | 0-0 | 34-22-81 | D04893P | | 29 | | TB0241X | D011 | BJ | | ALL | |
| 523Z | | | UW | 0-0 | 34-22-81 | D04893P | | 31 | | TB0241X | C012 | BJ | | ALL | |
| 524B | 24 | PW | UX | 5-0 | 34-22-91 | D04893P | | 50 | | TB0243Y | C010 | BJ | | 050-099, 150-156, 162-166 | |
| 524B | 24 | PW | UX | 5-0 | 34-22-91 | D04893P | | 26 | | TB0243Y | C010 | BJ | | 157, 167-199, 275-299 | |
| 524R | 24 | PW | UX | 0-0 | 34-22-91 | D04893P | | 49 | | TB0243Y | C009 | BJ | | 050-099, 150-156, 162-166 | |
| 524R | 24 | PW | UX | 0-0 | 34-22-91 | D04893P | | 25 | | TB0243Y | C009 | BJ | | 157, 167-199, 275-299 | |
| 524Z | | | UX | 0-0 | 34-22-91 | D04893P | | 51 | | TB0243X | C008 | BJ | | 050-099, 150-156, 162-166 | |
| 524Z | | | UX | 0-0 | 34-22-91 | D04893P | | 27 | | TB0243X | C008 | BJ | | 157, 167-199, 275-299 | |
| 525B | 24 | PW | UY | 5-0 | 34-22-91 | D04893P | | 53 | | TB0243Y | A010 | BJ | | ALL | |
| 525R | 24 | PW | UY | 0-0 | 34-22-91 | D04893P | | 52 | | TB0243Y | A009 | BJ | | ALL | |
| 525Z | | | UY | 0-0 | 34-22-91 | D04893P | | 54 | | TB0243X | B007 | BJ | | ALL | |
| 601 | 24 | PK | | 10-0 | 22-14-11 | D05107P | | 1 | | D04893P | 1 | | | ALL | |
| 602 | 24 | PK | | 10-0 | 22-14-11 | D05107P | | 2 | | D04893P | 6 | | | ALL | |
| 604 | 24 | PK | | 5-0 | 34-22-28 | TB0241Y | | A013 | BJ | D05813P | 7 | | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0030
Page 10
Jan 21/2005



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0031 | 286T0031 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | | |
| 605 | 24 | | PK | 10-0 | 34-12-22 | D05107P | | 4 | | | | | D04965P | 31 | | | ALL |
| 607 | 22 | | PA | 10-0 | 33-16-13 | D05107P | | 7 | | | | | TB0247Z | 10 | BJ | | ALL |
| 609 | 22 | | PQ | YI | 10-0 | 33-16-13 | D05107P | | 9 | | | | D05393P | 2 | | | ALL |
| 609Z | | | | YI | 0-0 | 33-16-13 | D05107P | DED | | | | | D05393P | DED | | | ALL |
| 611 | 22 | | PA | | 8-0 | 33-16-15 | TB0247Z | | 10 | BJ | | | D05309P | 2 | | | ALL |
| 612 | 22 | | PA | | 8-0 | 33-16-15 | TB0247Y | C004 | | BJ | | | D05309P | 1 | | | ALL |
| 613 | 22 | | PQ | YM | 5-0 | 33-16-12 | D05393P | | 5 | | | | TB0243Y | A014 | BJ | | ALL |
| 613Z | | | | YM | 0-0 | 33-16-12 | D05393P | DED | | | | | TB0243Y | DED | | | ALL |
| 614 | 22 | | PA | | 6-0 | 33-16-16 | D05020J | | 13 | | | | TB0247Z | 10 | BJ | | ALL |
| 615 | 22 | | PQ | YO | 8-0 | 33-16-16 | D05393P | | 7 | | | | D00477 | 3 | | | ALL |
| 615Z | | | | YO | 0-0 | 33-16-16 | D05393P | DED | | | | | D00477 | DED | | | ALL |
| 616 | 22 | | PA | | 8-0 | 33-16-16 | D00871 | | 5 | | | | TB0247Z | 10 | BJ | | ALL |
| 617 | 22 | | PA | | 8-0 | 33-16-16 | D00477 | | 9 | | | | TB0247Z | 10 | BJ | | ALL |
| 618 | 20 | | PA | | 8-0 | 33-42-11 | D00232 | | 5 | | | | D05399P | 11 | | | ALL |
| 619 | 22 | | PA | | 8-0 | 32-31-11 | D00232 | | 3 | | | | D06178P | 1 | | | ALL |
| 620 | 22 | | PA | | 8-0 | 32-31-11 | D00232 | | 4 | | | | D06178P | 2 | | | ALL |
| 623 | 24 | | PK | | 8-0 | 32-41-11 | D00238 | | 6 | | | | D06178P | 3 | | | ALL |
| 624 | 24 | | PK | | 8-0 | 32-41-11 | D00238 | | 3 | | | | D06178P | 4 | | | ALL |
| 625 | 24 | | PK | | 8-0 | 32-41-11 | D00238 | | 4 | | | | D06178P | 5 | | | ALL |
| 626 | 20 | | PA | | 5-0 | 32-41-11 | D00238 | | 5 | | | | GD03104 | S.. | 2 | | ALL |
| 627 | 24 | | PK | | 10-0 | 32-42-12 | D00224 | | 1 | | | | D06180P | 1 | | | ALL |
| 628 | 24 | | PK | | 8-0 | 32-42-12 | D00224 | | 11 | | | | SM00101 | | W | | ALL |
| 629 | 24 | | PK | | 8-0 | 32-42-12 | D00224 | | 12 | | | | SM00101 | | W | | ALL |
| 630 | 24 | | PK | | 8-0 | 32-42-12 | D00224 | | 26 | | | | SM00101 | | W | | ALL |
| 631 | 24 | | PK | | 8-0 | 32-42-12 | D00224 | | 27 | | | | SM00101 | | W | | ALL |
| 632 | 24 | | PK | | 8-0 | 32-42-12 | D00224 | | 28 | | | | SM00101 | | W | | ALL |
| 633 | 24 | | PK | | 5-0 | 32-42-12 | D06180P | | 2 | | | | SM00101 | | W | | ALL |
| 634 | 24 | | PK | | 10-0 | 32-42-12 | D00224 | | 37 | | | | D06180P | 3 | | | ALL |
| 635 | 24 | | PK | | 10-0 | 32-42-12 | D00224 | | 38 | | | | D06180P | 4 | | | ALL |
| 636 | 24 | | PK | | 10-0 | 32-42-12 | D00224 | | 39 | | | | D06180P | 5 | | | ALL |
| 637 | 24 | | PK | | 10-0 | 32-42-12 | D00224 | | 40 | | | | D06180P | 6 | | | ALL |
| 638 | 24 | | PK | | 10-0 | 32-42-12 | D00224 | | 41 | | | | D06180P | 7 | | | ALL |
| 639 | 24 | | PK | | 10-0 | 32-42-12 | D00224 | | 36 | | | | D06180P | 8 | | | ALL |
| 640 | 24 | | PK | | 10-0 | 32-42-12 | D00224 | | 23 | | | | D06180P | 9 | | | ALL |
| 641 | 24 | | PK | | 8-0 | 32-42-12 | D00224 | | 35 | | | | SM00102 | | W | | ALL |
| 642 | 24 | | PK | | 8-0 | 32-42-12 | D00224 | | 14 | | | | SM00102 | | W | | ALL |
| 643 | 24 | | PK | | 8-0 | 32-42-12 | D00224 | | 15 | | | | SM00102 | | W | | ALL |
| 644 | 24 | | PK | | 8-0 | 32-42-12 | D00224 | | 30 | | | | SM00102 | | W | | ALL |
| 645 | 24 | | PK | | 8-0 | 32-42-12 | D00224 | | 31 | | | | SM00102 | | W | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 11

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0031 | 286T0031 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | |
| 646 | 24 | | PK | 8-0 | 32-42-12 | D00224 | | 32 | | SM00102 | | | W | | ALL |
| 647 | 24 | | PK | 5-0 | 32-42-12 | D06180P | | 10 | | SM00102 | | | W | | ALL |
| 649 | 24 | | PK | 6-0 | 34-22-27 | D04391P | | 44 | | D05045P | 24 | | | | 050-099 |
| 649 | 24 | | PK | 7-0 | 34-22-27 | D05045P | | 24 | | D04391P | 44 | | | | 150-199, 275-299 |
| 650 | 22 | | PA | 13-0 | 31-41-11 | D04263P | | 10 | | D05113P | 1 | | | | ALL |
| 651 | 22 | | PA | 13-0 | 31-41-11 | D04263P | | 12 | | D05117P | 1 | | | | ALL |
| 652 | 24 | | PK | 11-0 | 31-41-16 | D05020J | | 4 | | TB0241Y | C003 | BJ | | | ALL |
| 653 | 24 | | PK | 11-0 | 31-41-16 | D05020J | | 5 | | TB0241Y | C004 | BJ | | | ALL |
| 654 | 24 | | PK | 10-0 | 32-42-12 | D00224 | | 9 | | D06180P | 12 | | | | ALL |
| 655 | 24 | | PK | 10-0 | 32-42-12 | D00224 | | 19 | | D06180P | 13 | | | | ALL |
| 656 | 24 | | PK | 10-0 | 32-42-12 | D00224 | | 16 | | D06180P | 14 | | | | ALL |
| 657 | 24 | | PK | 8-0 | 32-42-12 | D00224 | | 33 | | SM00104 | | | W | | ALL |
| 658 | 24 | | PK | 5-0 | 32-42-12 | D06180P | | 11 | | SM00104 | | | W | | ALL |
| 659 | 24 | | PK | 7-0 | 32-42-12 | D05107P | | 11 | | SM00104 | | | W | | ALL |
| 660 | 24 | | PK | 8-0 | 32-42-12 | D00224 | | 17 | | SM00103 | | | W | | ALL |
| 661 | 24 | | PK | 8-0 | 32-42-12 | D00224 | | 18 | | SM00103 | | | W | | ALL |
| 662 | 24 | | PK | 8-0 | 32-42-12 | D00224 | | 24 | | SM00103 | | | W | | ALL |
| 663 | 24 | | PK | 8-0 | 32-42-12 | D00224 | | 34 | | SM00103 | | | W | | ALL |
| 664 | 20 | | PA | 2-0 | 32-42-12 | SM00103 | | | W | GD03104 | | D.. | 2 | | ALL |
| 665 | 24 | | PV | 8-0 | 32-61-14 | D00232 | | 6 | | D06182P | | | 1 | | ALL |
| 665Z | | | | 0-0 | 32-61-14 | D00232 | | DED | | D06182P | | DED | | | ALL |
| 666 | 24 | | PK | 8-0 | 32-61-14 | D00232 | | 9 | | D06182P | | | 2 | | ALL |
| 667 | 20 | | PA | 8-0 | 32-61-14 | D00232 | | 7 | | GD03104 | | D.. | 2 | | ALL |
| 668 | 20 | | PA | 8-0 | 32-61-14 | D00232 | | 11 | | GD03104 | | D.. | 2 | | ALL |
| 671 | 20 | | PA | 8-0 | 73-21-14 | D10124 | | 9 | | GD03104 | | S.. | 2 | | ALL |
| 672 | 24 | | PK | 10-0 | 73-21-14 | D10124 | | 18 | | D06180P | | | 28 | | ALL |
| 673 | 22 | | PA | 10-0 | 79-33-11 | D05107P | | 13 | | D06180P | | | 15 | | ALL |
| 674 | 18 | | PA | 9-0 | 27-51-11 | D06182P | | 5 | DL | D05309P | | | 4 | DK | ALL |
| 675 | 22 | | PA | 9-0 | 27-51-11 | D06182P | | 6 | | D05309P | | | 5 | | ALL |
| 676 | 18 | | PA | 9-0 | 27-51-11 | D06182P | | 7 | DL | D05309P | | | 6 | DK | ALL |
| 677 | 20 | | PA | 9-0 | 27-51-11 | D06182P | | 8 | | D05309P | | | 7 | | ALL |
| 678 | 20 | | PA | 8-0 | 27-51-11 | D10032 | | 1 | | GD00071 | | D.. | 2 | | ALL |
| 679 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 2 | | D06182P | | | 9 | | ALL |
| 680 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 3 | | D06182P | | | 10 | | ALL |
| 681 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 4 | | D06182P | | | 11 | | ALL |
| 682 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 5 | | D06182P | | | 12 | | ALL |
| 683 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 6 | | D06182P | | | 13 | | ALL |
| 684 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 7 | | D06182P | | | 14 | | ALL |
| 685 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 8 | | D06182P | | | 15 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 12

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0031 | 286T0031 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | | |
| 686 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 9 | | | | | D06182P | 16 | | | ALL |
| 687 | 20 | | PA | 8-0 | 27-51-11 | D10032 | | 10 | | | | | GD00071 | D.. | 2 | | ALL |
| 688 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 12 | | | | | D06180P | 16 | | | ALL |
| 689 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 13 | | | | | D06180P | 17 | | | ALL |
| 690 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 14 | | | | | D06180P | 18 | | | ALL |
| 691 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 15 | | | | | D06180P | 19 | | | ALL |
| 692 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 16 | | | | | D06180P | 20 | | | ALL |
| 693 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 17 | | | | | D06180P | 21 | | | ALL |
| 694 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 18 | | | | | D06180P | 22 | | | ALL |
| 695 | 20 | | PA | 8-0 | 27-51-11 | D10032 | | 19 | | | | | GD00071 | D.. | 2 | | ALL |
| 696 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 21 | | | | | D06180P | 23 | | | ALL |
| 697 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 22 | | | | | D06180P | 24 | | | ALL |
| 698 | 24 | | PK | 9-0 | 27-51-11 | D10032 | | 23 | | | | | D06180P | 25 | | | ALL |
| 701 | 24 | | PK | 7-0 | 22-14-21 | D01365 | | 15 | | | | | D01365 | 4 | | | 050-099 |
| 701 | 24 | | PK | 1-0 | 22-14-21 | D01365 | | 15 | | | | | D01365 | 4 | | | 150-199, 275-299 |
| 702 | 24 | | PK | 5-0 | 22-14-21 | D00635 | | 9 | | | | | SM00047 | | | W | ALL |
| 703 | 24 | | PK | 5-0 | 22-14-21 | D00635 | | 8 | | | | | SM00047 | | | W | ALL |
| 704 | 24 | | PK | 5-0 | 22-14-21 | D00635 | | 2 | | | | | SM00047 | | | W | ALL |
| 709 | 24 | | PK | 7-0 | 34-61-26 | D05045P | | 1 | | | | | D04965P | 39 | | | ALL |
| 710 | 18 | | PA | 9-0 | 27-81-11 | D05309P | | 25 | DK | | | | D06182P | 17 | DL | | ALL |
| 711 | 22 | | PA | 9-0 | 27-81-11 | D05309P | | 27 | | | | | D06182P | 18 | | | ALL |
| 712 | 18 | | PA | 9-0 | 27-81-11 | D05309P | | 29 | DK | | | | D06182P | 19 | DL | | ALL |
| 713 | 22 | | PA | 9-0 | 27-81-11 | D05309P | | 31 | | | | | D06182P | 20 | | | ALL |
| 714 | 18 | | PA | 9-0 | 27-81-21 | D05309P | | 17 | DK | | | | D06178P | 14 | DL | | ALL |
| 715 | 18 | | PA | 9-0 | 27-81-21 | D05309P | | 19 | DK | | | | D06178P | 15 | DL | | ALL |
| 716 | 18 | | PA | 9-0 | 27-81-21 | D05309P | | 21 | DK | | | | D06178P | 16 | DL | | ALL |
| 717 | 20 | | PA | 9-0 | 27-81-21 | D05309P | | 23 | | | | | D06178P | 17 | | | ALL |
| 736 | 20 | | PA | 5-0 | 34-61-26 | D05045P | | 2 | | | | | GD00071 | D.. | 2 | | ALL |
| 737 | 20 | | PA | 5-0 | 34-61-26 | D05045P | | 5 | | | | | GD00071 | D.. | 2 | | ALL |
| 738 | 24 | | PK | 7-0 | 34-61-26 | D05045P | | 6 | | | | | D04965P | 29 | | | ALL |
| 739 | 20 | | PA | 5-0 | 34-61-26 | D05045P | | 15 | | | | | GD00071 | D.. | 2 | | 050-099 |
| 739 | 20 | | PA | 6-0 | 34-61-26 | D05045P | | 15 | | | | | GD00071 | D.. | 2 | | 150-199, 275-299 |
| 742 | 20 | | PA | 5-0 | 34-61-26 | D05045P | | 30 | | | | | GD00071 | D.. | 2 | | ALL |
| 743 | 24 | | PK | 7-0 | 34-61-26 | D05045P | | 18 | | | | | D04965P | 32 | | | ALL |
| 744 | 24 | | PK | 6-0 | 34-61-26 | D05813P | | 2 | | | | | SP00365 | | | 9 | 150-199, 275-299 |
| 745 | 20 | | PA | 7-0 | 31-31-26 | D05309P | | 10 | | | | | GD00077 | S.. | 2 | | 050-099 |
| 745 | 20 | | PA | 8-0 | 31-31-26 | D05309P | | 10 | | | | | GD00077 | S.. | 2 | | 150-199, 275-299 |
| 746 | 24 | | PK | 9-0 | 31-31-26 | D05309P | | 11 | | | | | D06182P | 3 | | | ALL |
| 757 | 22 | | PA | 6-0 | 34-45-14 | D04893P | | 7 | | | | | D00717 | 28 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 13

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0031 | 286T0031 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | |
| 758 | 24 | | PK | | 6-0 | 34-61-26 | D05045P | | 12 | | | D04893P | | 9 | | 050-099 |
| 758 | 24 | | PK | | 7-0 | 34-61-26 | D05045P | | 12 | | | D04893P | | 9 | | 155-199, 275-299 |
| 760 | 24 | | PK | | 12-0 | 34-61-24 | D04287P | | 5 | | | D04893P | | 8 | | 050-099 |
| 760 | 24 | | PK | | 12-0 | 34-61-16 | D04287P | | 5 | | | D04893P | | 8 | | 155-199, 275-299 |
| 762 | 22 | | PA | | 9-0 | 22-11-22 | D00477 | | 5 | | | D05423P | | 1 | | ALL |
| 763 | 22 | | PA | | 9-0 | 22-11-22 | D00477 | | 7 | | | D05423P | | 2 | | ALL |
| 764 | 22 | | PA | | 9-0 | 22-11-22 | D00477 | | 30 | | | D05423P | | 3 | | ALL |
| 765 | 20 | | PA | | 3-0 | 22-11-22 | D00477 | | 18 | | | GD00311 | D.. | 2 | | ALL |
| 766 | 20 | | PA | | 3-0 | 22-11-22 | D00477 | | 19 | | | GD00311 | S.. | 2 | | ALL |
| 768 | 20 | | PA | | 4-0 | 34-61-26 | D05045P | | 40 | | | GD03096 | D.. | 2 | | 051-099, 155-199, 275-299 |
| 769 | 20 | | PA | | 4-0 | 34-61-26 | D05045P | | 41 | | | GD03096 | D.. | 2 | | 051-099, 155-199, 277-299 |
| 769 | 20 | | PA | | 8-0 | 34-61-26 | D05045P | | 41 | | | GD03096 | D.. | 2 | | 275-276 |
| 770 | 20 | | PA | | 6-0 | 34-61-16 | D04287P | | 6 | | | GD00059 | D.. | 2 | | 051-099, 155-199, 275-299 |
| 771 | 20 | | PA | | 6-0 | 34-61-16 | D04287P | | 7 | | | GD00059 | D.. | 2 | | 051-099, 155-199, 275-299 |
| 773 | 22 | | PA | | 9-0 | 34-51-21 | D00159 | | 6 | | | D05417P | | 5 | | ALL |
| 774 | 20 | | PA | | 5-0 | 34-51-21 | D00159 | | 14 | | | GD00311 | D.. | 2 | | ALL |
| 775 | 24 | | PK | | 9-0 | 34-55-21 | D00159 | | 7 | | | D05417P | | 1 | | ALL |
| 776 | 20 | | PA | | 5-0 | 34-55-21 | D00871 | | 6 | | | GD00311 | D.. | 2 | | ALL |
| 777 | 20 | | PA | | 1-6 | 34-55-21 | D00871 | | 12 | | | GD00699 | S.. | E | | ALL |
| 778 | 20 | | PA | | 6-0 | 31-41-16 | D05020J | | 6 | | | GD00311 | D.. | 2 | | ALL |
| 779 | 20 | | PA | | 6-0 | 31-51-21 | D05020J | | 9 | | | GD00311 | D.. | 2 | | ALL |
| 780 | 24 | | PK | | 5-0 | 33-13-17 | D05399P | | 14 | | | TB0243Y | C015 | BJ | | ALL |
| 781 | 18 | | PA | | 8-0 | 33-13-17 | D00871 | | 1 | DK | | SP00349 | | 9 | | ALL |
| 782 | 18 | | PA | | 5-0 | 33-13-17 | D00871 | | 2 | DK | | GD00311 | A.. | 2 | | ALL |
| 783 | 24 | | PK | | 5-0 | 33-14-11 | D05399P | | 18 | | | TB0247Y | C001 | BJ | | ALL |
| 784 | 24 | | PK | | 6-0 | 33-14-11 | D05020J | | 10 | | | TB0247Y | C001 | BJ | | ALL |
| 785 | 24 | | PK | | 11-0 | 33-14-11 | D05016J | | 3 | | | TB0247Y | C001 | BJ | | ALL |
| 786 | 24 | | PK | | 7-0 | 33-14-11 | D05399P | | 19 | | | D05020J | | 11 | | ALL |
| 787 | 24 | | PK | | 11-0 | 33-14-11 | D05399P | | 20 | | | D05016J | | 4 | | ALL |
| 788 | 22 | | PA | | 5-0 | 33-16-12 | D05399P | | 3 | | | TB0247Y | C004 | BJ | | ALL |
| 789 | 22 | | PA | | 5-0 | 33-16-12 | D05399P | | 5 | | | TB0247Z | 10 | BJ | | ALL |
| 790 | 22 | | PQ | P0 | 6-0 | 33-16-16 | D05020J | | 12 | | | TB0243Y | A014 | BJ | | ALL |
| 790Z | | | | P0 | 0-0 | 33-16-16 | D05020J | | DED | | | TB0243Y | DED | | | ALL |
| 791 | 22 | | PQ | P1 | 8-0 | 33-16-16 | D00871 | | 4 | | | TB0243Y | A014 | BJ | | ALL |
| 791Z | | | | P1 | 0-0 | 33-16-16 | D00871 | | DED | | | TB0243Y | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 14

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|--|----|--|----------|----------|---------|----|-----|-------|---------|-------|---------|------|--------|-------|------|---------------------------------------|
| | | | | | Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type |
| W0031 | 286T0031 | | | P1, P3 AND P55 INSTRUMENT PANEL (continued) | | | | | | | | | | | | | | |
| 796 | 24 | | PK | | 8-0 | 32-61-14 | D00232 | | 8 | | | | D06182P | 22 | | | | ALL |
| 804 | 20 | | PA | | 5-0 | 34-22-27 | D05045P | | 44 | | | | GD00073 | D.. | 2 | | | ALL |
| 808 | 22 | | PA | | 12-0 | 34-22-36 | D04965P | | 30 | | | | SP00365 | | 9 | | | 050-099 |
| 808 | 22 | | PA | | 11-0 | 34-22-36 | D04965P | | 30 | | | | SP00365 | | 9 | | | 150-199, 275-299 |
| 810 | 22 | | PA | | 8-0 | 34-22-36 | D05309P | | 8 | | | | SP00365 | | 9 | | | ALL |
| 811 | 20 | | PA | | 4-0 | 34-22-36 | D05309P | | 9 | | | | GD00311 | D.. | 2 | | | ALL |
| 818 | 20 | | PA | | 3-0 | 22-11-22 | D00477 | | 11 | | | | GD00311 | D.. | 2 | | | ALL |
| 846 | 22 | | PA | | 7-0 | 34-12-62 | D05045P | | 49 | | | | D05393P | | 8 | | | ALL |
| 847 | 22 | | PA | | 7-0 | 34-12-62 | D05045P | | 47 | | | | D04965P | | 19 | | | ALL |
| 848 | 22 | | PA | | 7-0 | 34-12-62 | D05045P | | 48 | | | | D04965P | | 20 | | | ALL |
| 901 | 22 | | PA | | 2-0 | 34-22-92 | D00717 | | 18 | | | | D00717 | | 37 | | | 050-099, 150-152, 155-199, 275-299 |
| 927 | 20 | | PA | | 5-0 | 33-13-13 | SPZ0001 | | | S | | | D00238 | | 1 | | | 150, 152-199, 275-299 |
| FRA | | | | | 0-0 | 73-21-14 | D10124 | | | REF | | UI | D10124 | | 20 | | | 150-199, 275-299 |
| FRP | | | | | 0-0 | 73-21-14 | D10124 | | | | | UI | D10124 | | 20 | | | 050-099 |
| FRP | | | | | 0-0 | 34-13-21 | TB0243Y | | | REF | | FP | TB0243X | B004 | | BJ | | ALL |
| W0032 | 286T0032 | | | P11-S1-BUS DISTRIBUTION | | | | | | | | | | | | | | |
| 001 | 08 | | PA | | 5-0 | 24-54-71 | TB5022 | | 13 | E | | | C01510 | 2 | LA | * | | ALL |
| 002 | 08 | | PA | | 2-0 | 24-54-71 | C01428 | | 2 | LA | * | | C01184 | 1 | LA | * | | 050-099, 275-299 |
| 002 | 08 | | PA | | 3-0 | 24-54-71 | C01428 | | 2 | LA | * | | C01184 | 1 | LA | * | | 150-199 |
| 003 | 08 | | PA | | 2-0 | 24-54-71 | C01510 | | 2 | LA | * | | C01428 | 2 | LA | * | | ALL |
| 004 | 08 | | PA | | 3-0 | 24-54-71 | C00793 | | 2 | LA | * | | C01184 | 1 | LA | * | | 050-099 |
| 004 | 08 | | PA | | 2-0 | 24-54-71 | C01184 | | 1 | LA | * | | C00646 | 1 | LA | * | | 150-199 |
| 004 | 08 | | PA | | 2-0 | 24-54-71 | C01184 | | 1 | LA | * | | C00793 | 2 | LA | * | | 275-299 |
| 005 | 08 | | PA | | 3-0 | 24-54-71 | C00646 | | 1 | LA | * | | C00793 | 2 | LA | * | | 150-199 |
| 007 | 08 | | PA | | 2-0 | 24-54-71 | C00793 | | 2 | LA | * | | C01322 | 1 | LA | * | | ALL |
| 009 | 08 | | PA | | 2-0 | 24-54-71 | C01010 | | 1 | D | | | C01308 | 1 | D | | | 277-299 |
| 010 | 08 | | PA | | 2-0 | 24-54-71 | C01322 | | 1 | LA | * | | C01512 | 2 | D | | | 050-099 |
| 010 | 08 | | PA | | 2-0 | 24-54-71 | C01512 | | 2 | D | | | C01322 | 1 | LA | * | | 150-199, 275-299 |
| 011 | 08 | | PA | | 5-0 | 24-54-71 | TB5020 | | 15 | E | | | TB5022 | 13 | E | | | ALL |
| 012 | 08 | | PA | | 6-0 | 24-54-71 | TB5020 | | 15 | E | | | C01427 | 2 | D | | | ALL |
| 031 | 08 | | PA | | 4-0 | 24-54-71 | C01069 | | 2 | D | | | TB5022 | 13 | E | | | ALL |
| 090 | 12 | | PA | | 6-0 | 24-54-73 | TB5020 | | 11 | E | | | C01480 | 2 | D | * | | ALL |
| 092 | 12 | | PA | | 2-0 | 24-54-73 | C01480 | | 2 | D | * | | C00826 | 2 | D | * | | ALL |
| 093 | 12 | | PA | | 2-0 | 24-54-73 | C00826 | | 2 | D | * | | C00811 | 2 | D | * | | ALL |
| 094 | 12 | | PA | | 2-0 | 24-54-73 | C00811 | | 2 | D | * | | C00544 | 1 | D | * | | ALL |
| 095 | 12 | | PA | | 2-0 | 24-54-73 | C00544 | | 1 | D | * | | C01534 | 1 | D | * | | ALL |
| 096 | 12 | | PA | | 2-0 | 24-54-73 | C01534 | | 1 | D | * | | C01533 | 1 | D | * | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 15

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0032 | 286T0032 | | | P11-S1-BUS DISTRIBUTION (continued) | | | | | | | | | | | |
| 097 | 12 | | PA | 2-0 | 24-54-73 | C01533 | 1 | D | * | C01026 | 1 | D | * | ALL | |
| 098 | 12 | | PA | 3-0 | 24-54-73 | C01026 | 1 | D | * | C01576 | 2 | D | * | ALL | |
| 099 | 12 | | PA | 1-0 | 24-54-73 | C00725 | 2 | D | * | C01212 | 2 | D | * | 050-099 | |
| 099 | 12 | | PA | 3-0 | 24-54-73 | C00567 | 2 | D | * | C01212 | 2 | D | * | 150-199, 275-299 | |
| 100 | 12 | | PA | 2-0 | 24-54-73 | C01212 | 2 | D | * | C00619 | 1 | D | * | 050-099 | |
| 100 | 12 | | PA | 2-0 | 24-54-73 | C00725 | 1 | D | * | C00619 | 1 | D | * | 150-199 | |
| 100 | 12 | | PA | 2-0 | 24-54-73 | C00725 | 2 | D | * | C00619 | 1 | D | * | 275-299 | |
| 101 | 12 | | PA | 2-0 | 24-54-73 | C00619 | 1 | D | * | C00591 | 1 | D | * | ALL | |
| 102 | 12 | | PA | 2-0 | 24-54-73 | C00591 | 1 | D | * | C00521 | 1 | D | * | ALL | |
| 103 | 14 | | PA | 6-0 | 24-54-73 | TB5020 | 10 | E | * | C01435 | 2 | D | * | ALL | |
| 104 | 14 | | PA | 2-0 | 24-54-73 | C01435 | 2 | D | * | C00892 | 2 | D | * | ALL | |
| 105 | 14 | | PA | 2-0 | 24-54-73 | C00892 | 2 | D | * | C01538 | 1 | D | * | ALL | |
| 106 | 14 | | PA | 2-0 | 24-54-73 | C01538 | 1 | D | * | C01537 | 1 | D | * | ALL | |
| 107 | 14 | | PA | 2-0 | 24-54-73 | C01537 | 1 | D | * | C01037 | 1 | D | * | ALL | |
| 108 | 14 | | PA | 3-0 | 24-54-73 | C01037 | 1 | D | * | C00566 | 2 | D | * | ALL | |
| 109 | 14 | | PA | 2-0 | 24-54-73 | C00566 | 2 | D | * | C04205 | 2 | D | * | ALL | |
| 110 | 14 | | PA | 2-0 | 24-54-73 | C04205 | 2 | D | * | C01283 | 2 | D | * | ALL | |
| 112 | 14 | | PA | 2-0 | 24-54-73 | C01283 | 2 | D | * | C00595 | 1 | D | * | ALL | |
| 113 | 14 | | PA | 2-0 | 24-54-73 | C00606 | 1 | D | * | C00635 | 1 | D | * | ALL | |
| 114 | 14 | | PA | 2-0 | 24-54-73 | C00635 | 1 | D | * | C00625 | 1 | D | * | ALL | |
| 115 | 14 | | PA | 2-0 | 24-54-73 | C00606 | 1 | D | * | C00595 | 1 | D | * | ALL | |
| 116 | 12 | | PA | 1-0 | 24-54-73 | C01404 | 2 | D | * | C01482 | 2 | D | * | 050-099 | |
| 116 | 12 | | PA | 1-0 | 24-54-73 | C01482 | 2 | D | * | C01404 | 2 | D | * | 150-199, 275-299 | |
| 117 | 12 | | PA | 2-0 | 24-54-73 | C00725 | 2 | D | * | C00567 | 2 | D | * | 050-099 | |
| 117 | 12 | | PA | 2-0 | 24-54-73 | C00725 | 1 | D | * | C01212 | 2 | D | * | 150-199 | |
| 117 | 12 | | PA | 2-0 | 24-54-73 | C00725 | 2 | D | * | C01212 | 2 | D | * | 275-299 | |
| 125 | 12 | | PA | 3-0 | 24-54-73 | C01576 | 2 | D | * | C00567 | 2 | D | * | ALL | |
| W0033 | 286T0033 | | | P3-3 F/O INSTR PNL-R | | | | | | | | | | | |
| 001 | 24 | | PK | 3-0 | 34-22-92 | D05045J | 21 | | | S00012 | 2 | 1A | | ALL | |
| 002 | 20 | | PA | 3-0 | 34-22-92 | D05045J | 22 | | | S00012 | 3 | 1A | | ALL | |
| 003 | 24 | | PK | 3-0 | 34-22-27 | D05045J | 10 | | | S00012 | 6 | 1A | | ALL | |
| 004 | 20 | | PA | 3-0 | 34-22-27 | D05045J | 11 | | | S00012 | 5 | 1A | | ALL | |
| 005 | 24 | | PK | 3-0 | 34-22-27 | D05045J | 7 | | | S00009 | B | 1A | | ALL | |
| 006 | 24 | | PK | 3-0 | 34-22-27 | D05045J | 8 | | | S00009 | D | 1A | | ALL | |
| 007 | 20 | | PA | 3-0 | 34-22-27 | D05045J | 9 | | | S00009 | A | 1A | | ALL | |
| 008 | 20 | | PA | 3-0 | 34-22-27 | D05045J | 17 | | | S00010 | BC | 1A | | 050, 150-154, 275-276 | |
| 008 | 20 | | PA | 3-0 | 34-22-27 | D05045J | 17 | | | S00010 | AC | 1A | | 051-099, 155-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W0030
Page 16
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0033 | 286T0033 | | | P3-3 F/O INSTR PNL-R (continued) | | | | | | | | | | | | | |
| 009 | 24 | | PK | 3-0 | 34-22-27 | D05045J | | 16 | | | | | S00010 | BA | 1A | | 050, 150-154, 275-276 |
| 009 | 24 | | PK | 3-0 | 34-22-27 | D05045J | | 16 | | | | | S00010 | AA | 1A | | 051-099, 155-199, 277-299 |
| 010 | 20 | | PA | 3-0 | 34-22-38 | D05045J | | 28 | | | | | S00011 | 6 | 1A | | ALL |
| 011 | 22 | | PA | 3-0 | 34-22-38 | D05045J | | 29 | | | | | S00011 | 5 | 1A | | ALL |
| 012 | 24 | | PK | 3-0 | 34-21-31 | S00012 | | 1 | 1A | | | | D05045J | 27 | | | ALL |
| 013 | 22 | | PA | 3-0 | 34-32-11 | D05043J | | 7 | | | | | L00590 | 2 | 1A | | ALL |
| 014 | 22 | | PA | 3-0 | 34-32-11 | D05043J | | 6 | | | | | L00589 | 2 | 1A | | ALL |
| 015 | 22 | | PA | 3-0 | 34-32-11 | D05043J | | 5 | | | | | L00588 | 2 | 1A | | ALL |
| 016 | 20 | | PA | 3-0 | 34-22-81 | D05043J | | 2 | | | | | S00012 | 11 | 1A | | ALL |
| 017 | 24 | | PK | 3-0 | 34-22-81 | D05043J | | 1 | | | | | S00012 | 12 | 1A | | ALL |
| 018 | 24 | | PK | 3-0 | 34-22-37 | D05043J | | 3 | | | | | S00011 | 7 | 1A | | ALL |
| 019 | 24 | | PK | 3-0 | 34-22-37 | D05045J | | 4 | | | | | S00011 | 9 | 1A | | ALL |
| 023 | 22 | | PQ | AW | 3-0 | 33-16-15 | L00588 | 1 | 1A | | | | SM00002 | | W | | ALL |
| 023Z | | | AW | | 0-0 | 33-16-15 | L00588 | | DED | | | | SM00002 | DED | | | ALL |
| 024 | 22 | | PQ | AX | 3-0 | 33-16-15 | L00588 | 3 | 1A | | | | SM00001 | | W | | ALL |
| 024Z | | | AX | | 0-0 | 33-16-15 | L00588 | | DED | | | | SM00001 | DED | | | ALL |
| 025 | 22 | | PQ | AY | 3-0 | 33-16-15 | L00589 | 1 | 1A | | | | SM00002 | | W | | ALL |
| 025Z | | | AY | | 0-0 | 33-16-15 | L00589 | | DED | | | | SM00002 | DED | | | ALL |
| 026 | 22 | | PQ | BA | 3-0 | 33-16-15 | L00589 | 3 | 1A | | | | SM00001 | | W | | ALL |
| 026Z | | | BA | | 0-0 | 33-16-15 | L00589 | | DED | | | | SM00001 | DED | | | ALL |
| 027 | 22 | | PQ | BB | 3-0 | 33-16-15 | L00590 | 1 | 1A | | | | SM00002 | | W | | ALL |
| 027Z | | | BB | | 0-0 | 33-16-15 | L00590 | | DED | | | | SM00002 | DED | | | ALL |
| 028 | 22 | | PQ | BC | 3-0 | 33-16-15 | L00590 | 3 | 1A | | | | SM00001 | | W | | ALL |
| 028Z | | | BC | | 0-0 | 33-16-15 | L00590 | | DED | | | | SM00001 | DED | | | ALL |
| 029 | 22 | | PQ | BD | 2-0 | 33-16-15 | D05043J | 10 | | | | | SM00001 | | W | | ALL |
| 029Z | | | BD | | 0-0 | 33-16-15 | D05043J | | DED | | | | SM00001 | DED | | | ALL |
| 030 | 22 | | PQ | BE | 2-0 | 33-16-15 | D05043J | 11 | | | | | SM00002 | | W | | ALL |
| 030Z | | | BE | | 0-0 | 33-16-15 | D05043J | | DED | | | | SM00002 | DED | | | ALL |
| 041 | 20 | | PA | | 2-0 | 33-13-13 | D05045J | 38 | | | | | SM00005 | | W | | ALL |
| 042 | 20 | | PA | | 2-0 | 33-13-13 | D05045J | 39 | | | | | SM00006 | | W | | ALL |
| 044 | 20 | | PA | | 3-0 | 34-13-21 | S00483 | 2 | 1A | | | | D05045J | 26 | | | ALL |
| 046 | 20 | | PA | | 3-0 | 34-12-62 | S00483 | 3 | 1A | | | | D05045J | 23 | | | ALL |
| 047 | 22 | | PA | | 3-0 | 34-12-62 | S00483 | 6 | 1A | | | | D05045J | 25 | | | ALL |
| 050 | 24 | | PK | | 3-0 | 22-41-13 | D05043J | 4 | | | | | S00009 | G | 1A | | ALL |
| 051 | 24 | | PK | | 3-0 | 22-41-13 | D05045J | 32 | | | | | S00009 | H | 1A | | ALL |
| 052 | 24 | | PK | | 3-0 | 22-41-13 | D05045J | 31 | | | | | S00009 | J | 1A | | ALL |
| 053 | 24 | | PK | | 3-0 | 22-41-13 | D05045J | 33 | | | | | S00009 | F | 1A | | ALL |
| 054 | 22 | | PA | | 3-0 | 34-22-26 | D05045J | 34 | | | | | S00011 | 12 | 1A | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 17

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0033 | 286T0033 | | | P3-3 F/O INSTR PNL-R (continued) | | | | | | | | | | | |
| 055 | 20 | | PA | | 3-0 | 34-22-26 | D05045J | | | | S00011 | 11 | 1A | | ALL |
| 056 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | AA | 1A | | D05045J | 1 | | | 050, 150-154 |
| 057 | 20 | | PA | | 2-0 | 33-13-13 | SM00005 | | W | | L00489 | =P | B | | ALL |
| 058 | 20 | | PA | | 2-0 | 33-13-13 | SM00005 | | W | | S00483 | 13 | 1A | | ALL |
| 060 | 20 | | PA | | 2-0 | 33-13-13 | SM00005 | | W | | S00011 | 13 | 1A | | ALL |
| 061 | 20 | | PA | | 2-0 | 33-13-13 | SM00005 | | W | | S00012 | 13 | 1A | | ALL |
| 062 | 20 | | PA | | 2-0 | 33-13-13 | SM00006 | | W | | GDX0001 | A.. | E | | ALL |
| 063 | 20 | | PA | | 2-0 | 33-13-13 | SM00006 | | W | | S00483 | 15 | 1A | | ALL |
| 065 | 20 | | PA | | 2-0 | 33-13-13 | SM00006 | | W | | S00011 | 15 | 1A | | ALL |
| 066 | 20 | | PA | | 2-0 | 33-13-13 | SM00006 | | W | | S00012 | 15 | 1A | | ALL |
| 067 | 24 | | PK | | 3-0 | 32-42-11 | D05045J | | 36 | | S00012 | 8 | 1A | | ALL |
| 068 | 24 | | PK | | 3-0 | 32-42-11 | D05045J | | 37 | | S00012 | 9 | 1A | | ALL |
| 069 | 22 | | PA | | 3-0 | 34-12-62 | D05045J | | 3 | | S00483 | 5 | 1A | | ALL |
| 070 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | AB | 1A | | D05045J | 2 | | | 050, 150-154 |
| 071 | 20 | | PA | | 3-0 | 34-22-27 | S00011 | | 3 | 1A | D05045J | 44 | | | ALL |
| 072 | 22 | | PA | | 3-0 | 34-22-27 | S00011 | | 2 | 1A | D05045J | 55 | | | ALL |
| 075 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | AD | 1A | | D05045J | 5 | | | 050, 150-154 |
| 076 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | AF | 1A | | D05045J | 6 | | | 050, 150-154 |
| 077 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | AJ | 1A | | D05045J | 15 | | | 050, 150-154 |
| 078 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | BG | 1A | | D05045J | 30 | | | 050, 150-154 |
| 079 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | BF | 1A | | D05045J | 18 | | | 050, 150-154 |
| 094 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | AH | 1A | | D05045J | 1 | | | 051-099, 155-199, 275-299 |
| 095 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | AK | 1A | | D05045J | 2 | | | 051-099, 155-199, 275-299 |
| 096 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | AJ | 1A | | D05045J | 5 | | | 051-099, 155-199, 275-299 |
| 097 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | BH | 1A | | D05045J | 18 | | | 051-099, 155-199, 275-299 |
| 098 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | BK | 1A | | D05045J | 30 | | | 051-099, 155-199, 275-299 |
| 099 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | AG | 1A | | D05045J | 15 | | | 051-099, 155-199, 275-299 |
| 102 | 24 | | PK | | 3-0 | 34-22-27 | S00483 | | 1 | 1A | D05045J | 24 | | | ALL |
| 104 | 24 | | PK | | 3-0 | 34-61-26 | S00010 | AE | 1A | | D05045J | 6 | | | 051-099, 155-199, 275-299 |
| 105 | 20 | | PA | | 3-0 | 34-61-26 | S00010 | BE | 1A | | D05045J | 12 | | | 051-099, 155-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0030
Page 18
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0033 | 286T0033 | | | | P3-3 F/O INSTR PNL-R (continued) | | | | | | | | | | |
| 106 | 20 | | PA | 3-0 | 34-61-26 | S00010 | | BF | 1A | | D05045J | 40 | | | 051-099, 155-199, 275-299 |
| 107 | 20 | | PA | 3-0 | 34-61-26 | S00010 | | BG | 1A | | D05045J | 41 | | | 051-099, 155-199, 275-299 |
| 108 | 20 | | PA | 3-0 | 34-61-26 | S00010 | | BA | 1A | | D05043J | 9 | | | 051-099, 155-199, 277-299 |
| 108 | 20 | | PA | 3-0 | 34-61-26 | S00010 | | AA | 1A | | D05043J | 9 | | | 275-276 |
| 109 | 20 | | PA | 3-0 | 34-61-26 | S00010 | | BC | 1A | | D05043J | 12 | | | 051-099, 155-199, 277-299 |
| 109 | 20 | | PA | 3-0 | 34-61-26 | S00010 | | AC | 1A | | D05043J | 12 | | | 275-276 |
| 110 | 20 | | PA | 3-0 | 34-61-26 | S00010 | | BD | 1A | | D05043J | 13 | | | 051-099, 155-199, 277-299 |
| 110 | 20 | | PA | 3-0 | 34-61-26 | S00010 | | AD | 1A | | D05043J | 13 | | | 275-276 |
| 126 | 22 | | PA | 6-0 | 34-12-62 | S00483 | | 12 | 1A | | D05045J | 49 | | | 050, 150-154, 275-276 |
| 126 | 22 | | PA | 2-6 | 34-12-62 | S00483 | | 12 | 1A | | D05045J | 49 | | | 051-099, 155-199, 277-299 |
| 127 | 22 | | PA | 6-0 | 34-12-62 | S00483 | | 10 | 1A | | D05045J | 47 | | | 050, 150-154, 275-276 |
| 127 | 22 | | PA | 2-6 | 34-12-62 | S00483 | | 10 | 1A | | D05045J | 47 | | | 051-099, 155-199, 277-299 |
| 128 | 22 | | PA | 6-0 | 34-12-62 | S00483 | | 11 | 1A | | D05045J | 48 | | | 050, 150-154, 275-276 |
| 128 | 22 | | PA | 2-6 | 34-12-62 | S00483 | | 11 | 1A | | D05045J | 48 | | | 051-099, 155-199, 277-299 |
| W0034 | 286T0034 | | | | P-11 OVERHEAD CIRCUIT BREAKER PANEL LIGHTS | | | | | | | | | | |
| 002 | 20 | | PA | 2-0 | 33-13-19 | L00499 | | =P | B | | L00500 | =P | B | * | ALL |
| 003 | 20 | | PA | 2-0 | 33-13-19 | L00500 | | =P | B | | L00501 | =P | B | * | ALL |
| 004 | 20 | | PA | 2-0 | 33-13-19 | L00501 | | =P | B | * | L00502 | =P | B | * | ALL |
| 005 | 20 | | PA | 2-0 | 33-13-19 | L00502 | | =P | B | * | L00503 | =P | B | | ALL |
| 007 | 20 | | PA | 2-0 | 33-13-19 | L00504 | | =P | B | | L00505 | =P | B | | ALL |
| 009 | 20 | | PA | 2-0 | 33-13-19 | L00506 | | =P | B | | L00507 | =P | B | * | ALL |
| 010 | 20 | | PA | 2-0 | 33-13-19 | L00507 | | =P | B | * | L00508 | =P | B | * | ALL |
| 011 | 20 | | PA | 2-0 | 33-13-19 | L00508 | | =P | B | * | L00509 | =P | B | * | ALL |
| 012 | 20 | | PA | 2-0 | 33-13-19 | L00509 | | =P | B | * | L00510 | =P | B | | ALL |
| 014 | 20 | | PA | 2-0 | 33-13-19 | L00511 | | =P | B | | L00512 | =P | B | | ALL |
| 016 | 20 | | PA | 2-0 | 33-13-19 | L00513 | | =P | B | | L00514 | =P | B | * | ALL |
| 017 | 20 | | PA | 2-0 | 33-13-19 | L00514 | | =P | B | * | L00515 | =P | B | * | ALL |
| 018 | 20 | | PA | 2-0 | 33-13-19 | L00515 | | =P | B | * | L00516 | =P | B | * | ALL |
| 019 | 20 | | PA | 2-0 | 33-13-19 | L00516 | | =P | B | * | L00517 | =P | B | | ALL |
| 021 | 20 | | PA | 2-0 | 33-13-19 | L00518 | | =P | B | | L00519 | =P | B | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 19

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0034 | 286T0034 | | | P-11 OVERHEAD CIRCUIT BREAKER PANEL LIGHTS (continued) | | | | | | | | | | | |
| 023 | 20 | | PA | | 2-0 | 33-13-19 | L00520 | =P | B | | L00521 | =P | B | * | ALL |
| 024 | 20 | | PA | | 2-0 | 33-13-19 | L00521 | =P | B | * | L00522 | =P | B | * | ALL |
| 025 | 20 | | PA | | 2-0 | 33-13-19 | L00522 | =P | B | * | L00523 | =P | B | * | ALL |
| 026 | 20 | | PA | | 2-0 | 33-13-19 | L00523 | =P | B | * | L00524 | =P | B | | ALL |
| 028 | 20 | | PA | | 2-0 | 33-13-19 | L00525 | =P | B | | L00526 | =P | B | | ALL |
| 030 | 20 | | PA | | 2-0 | 33-13-19 | L00527 | =P | B | | L00528 | =P | B | * | ALL |
| 031 | 20 | | PA | | 2-0 | 33-13-19 | L00528 | =P | B | * | L00529 | =P | B | * | ALL |
| 032 | 20 | | PA | | 2-0 | 33-13-19 | L00529 | =P | B | * | L00530 | =P | B | * | ALL |
| 033 | 20 | | PA | | 2-0 | 33-13-19 | L00530 | =P | B | * | L00531 | =P | B | | ALL |
| 035 | 20 | | PA | | 2-0 | 33-13-19 | L00532 | =P | B | | L00533 | =P | B | | ALL |
| 037 | 20 | | PA | | 2-0 | 33-13-19 | L00534 | =P | B | | L00535 | =P | B | * | ALL |
| 038 | 20 | | PA | | 2-0 | 33-13-19 | L00535 | =P | B | * | L00536 | =P | B | * | ALL |
| 039 | 20 | | PA | | 2-0 | 33-13-19 | L00536 | =P | B | * | L00537 | =P | B | * | ALL |
| 040 | 20 | | PA | | 2-0 | 33-13-19 | L00537 | =P | B | * | L00538 | =P | B | | ALL |
| 042 | 20 | | PA | | 2-0 | 33-13-19 | L00539 | =P | B | | L00540 | =P | B | | ALL |
| W0035 | 286T0035 | | | P3-1 F/O INSTR PNL-L | | | | | | | | | | | |
| 001 | 24 | | PK | | 1-5 | 31-51-31 | D05305J | | 1 | | S00604 | | 2 | 1A | ALL |
| 002 | 20 | | PA | | 1-5 | 31-51-31 | D05305J | | 2 | | S00604 | | 3 | 1A | ALL |
| 003 | 24 | | PK | | 1-5 | 34-46-12 | D05305J | | 3 | | S00604 | | 8 | 1A | ALL |
| 004 | 20 | | PA | | 1-5 | 34-46-12 | D05305J | | 4 | | S00604 | | 9 | 1A | ALL |
| 005 | 24 | | PK | | 1-5 | 34-46-12 | D05305J | | 5 | | S00603 | | 8 | 1A | ALL |
| 006 | 20 | | PA | | 1-5 | 34-46-12 | S00603 | | 9 | 1A | D05305J | | 6 | | ALL |
| 007 | 24 | | PV | AG | 2-6 | 32-61-14 | L00654 | | 5 | 1A | D05305J | | 23 | | ALL |
| 007Z | | | | AG | 0-0 | 32-61-14 | L00654 | DED | | | D05305J | DED | | | ALL |
| 008 | | 24 | PV | AH | 2-6 | 32-61-14 | L00652 | | 5 | 1A | D05305J | | 24 | | ALL |
| 008Z | | | | AH | 0-0 | 32-61-14 | L00652 | DED | | | D05305J | DED | | | ALL |
| 009 | | 24 | PV | AI | 2-6 | 32-61-14 | L00653 | | 5 | 1A | D05305J | | 25 | | ALL |
| 009Z | | | | AI | 0-0 | 32-61-14 | L00653 | DED | | | D05305J | DED | | | ALL |
| 013 | 18 | | PA | | 0-11 | 33-13-13 | D05305J | | 9 | DL | SM00003 | | | W | ALL |
| 014 | 18 | | PA | | 0-11 | 33-13-13 | D05305J | | 10 | DL | SM00004 | | | W | ALL |
| 015 | 18 | | PA | | 0-11 | 33-13-13 | D04515J | | 9 | DL | SM00005 | | | W | ALL |
| 016 | 18 | | PA | | 0-11 | 33-13-13 | D05305J | | 12 | DL | SM00006 | | | W | ALL |
| 019 | 20 | | PA | | 1-2 | 33-13-13 | S00601 | | 13 | 1A | SM00003 | | | W | ALL |
| 020 | 20 | | PA | | 1-2 | 33-13-13 | S00601 | | 15 | 1A | SM00004 | | | W | ALL |
| 021 | 18 | | PA | | 1-3 | 33-13-13 | L00491 | =P | B | | SM00003 | | | W | ALL |
| 022 | 20 | | PA | | 1-2 | 33-13-13 | S00602 | | 13 | 1A | SM00003 | | | W | ALL |
| 023 | 20 | | PA | | 1-2 | 33-13-13 | S00602 | | 15 | 1A | SM00004 | | | W | ALL |
| 026 | 20 | | PA | | 1-2 | 33-13-13 | S00603 | | 13 | 1A | SM00005 | | | W | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0030
 Page 20
 May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0035 | 286T0035 | | | P3-1 F/O INSTR PNL-L (continued) | | | | | | | | | | | | | | |
| 027 | 20 | | PA | | 1-2 | 33-13-13 | S00603 | | 15 | 1A | | | | SM00006 | | W | | ALL |
| 028 | 20 | | PA | | 1-2 | 33-13-13 | S00604 | | 13 | 1A | | | | SM00005 | | W | | ALL |
| 029 | 20 | | PA | | 1-3 | 33-13-13 | S00604 | | 15 | 1A | | | | SM00006 | | W | | ALL |
| 030 | 22 | | PQ | BE | 2-4 | 33-16-15 | L00660 | | 1 | 1A | | | | SM00007 | | W | | ALL |
| 030Z | | | | BE | 0-0 | 33-16-15 | L00660 | | | | DED | | | SM00007 | DED | | | ALL |
| 031 | 22 | | PQ | BF | 1-2 | 33-16-15 | D05309J | | 1 | | | | | SM00007 | | W | | ALL |
| 031Z | | | | BF | 0-0 | 33-16-15 | D05309J | | | | DED | | | SM00007 | DED | | | ALL |
| 032 | 22 | | PQ | BG | 2-4 | 33-16-15 | L00661 | | 1 | 1A | | | | SM00007 | | W | | ALL |
| 032Z | | | | BG | 0-0 | 33-16-15 | L00661 | | | | DED | | | SM00007 | DED | | | ALL |
| 033 | 22 | | PQ | BH | 2-4 | 33-16-15 | L00660 | | 3 | 1A | | | | SM00008 | | W | | ALL |
| 033Z | | | | BH | 0-0 | 33-16-15 | L00660 | | | | DED | | | SM00008 | DED | | | ALL |
| 034 | 22 | | PQ | BI | 1-2 | 33-16-15 | D05309J | | 2 | | | | | SM00008 | | W | | ALL |
| 034Z | | | | BI | 0-0 | 33-16-15 | D05309J | | | | DED | | | SM00008 | DED | | | ALL |
| 035 | 22 | | PQ | BJ | 2-4 | 33-16-15 | L00661 | | 3 | 1A | | | | SM00008 | | W | | ALL |
| 035Z | | | | BJ | 0-0 | 33-16-15 | L00661 | | | | DED | | | SM00008 | DED | | | ALL |
| 036 | 22 | | PQ | BK | 2-5 | 33-16-15 | L00680 | | 1 | 1A | | | | D04515J | | 16 | | ALL |
| 036Z | | | | BK | 0-0 | 33-16-15 | L00680 | | | | DED | | | D04515J | DED | | | ALL |
| 037 | 22 | | PQ | BL | 2-2 | 33-16-15 | L00680 | | 3 | 1A | | | | SM00012 | | W | | ALL |
| 037Z | | | | BL | 0-0 | 33-16-15 | L00680 | | | | DED | | | SM00012 | DED | | | ALL |
| 038 | 22 | | PA | | 2-3 | 33-16-15 | L00663 | | 3 | 1A | | | | SM00001 | | W | | ALL |
| 041 | 22 | | PA | | 2-6 | 33-16-15 | L00663 | | 1 | 1A | | | | D05305J | | 15 | | ALL |
| 043 | 22 | | PA | | 2-6 | 33-16-15 | L00804 | | 1 | 1A | | | | D05305J | | 40 | | 150-199, 275-299 |
| 044 | 22 | | PA | | 0-11 | 33-16-15 | D04515J | | 10 | | | | | SM00011 | | W | | ALL |
| 045 | 22 | | PQ | BT | 2-4 | 33-16-15 | L00657 | | 1 | 1A | | | | SM00011 | | W | | ALL |
| 045Z | | | | BT | 0-0 | 33-16-15 | L00657 | | | | DED | | | SM00011 | DED | | | ALL |
| 046 | 22 | | PQ | BU | 2-4 | 33-16-15 | L00654 | | 1 | 1A | | | | SM00011 | | W | | ALL |
| 046Z | | | | BU | 0-0 | 33-16-15 | L00654 | | | | DED | | | SM00011 | DED | | | ALL |
| 047 | 22 | | PQ | BV | 2-3 | 33-16-15 | L00652 | | 1 | 1A | | | | SM00011 | | W | | ALL |
| 047Z | | | | BV | 0-0 | 33-16-15 | L00652 | | | | DED | | | SM00011 | DED | | | ALL |
| 048 | 22 | | PQ | BW | 2-4 | 33-16-15 | L00653 | | 1 | 1A | | | | SM00011 | | W | | ALL |
| 048Z | | | | BW | 0-0 | 33-16-15 | L00653 | | | | DED | | | SM00011 | DED | | | ALL |
| 049 | 22 | | PQ | BX | 2-3 | 33-16-15 | L00658 | | 1 | 1A | | | | SM00011 | | W | | ALL |
| 049Z | | | | BX | 0-0 | 33-16-15 | L00658 | | | | DED | | | SM00011 | DED | | | ALL |
| 051 | 22 | | PA | | 0-11 | 33-16-15 | D04515J | | 11 | | | | | SM00012 | | W | | ALL |
| 052 | 22 | | PQ | CB | 2-4 | 33-16-15 | L00657 | | 3 | 1A | | | | SM00012 | | W | | ALL |
| 052Z | | | | CB | 0-0 | 33-16-15 | L00657 | | | | DED | | | SM00012 | DED | | | ALL |
| 053 | 22 | | PQ | CC | 2-4 | 33-16-15 | L00654 | | 3 | 1A | | | | SM00012 | | W | | ALL |
| 053Z | | | | CC | 0-0 | 33-16-15 | L00654 | | | | DED | | | SM00012 | DED | | | ALL |
| 054 | 22 | | PQ | CD | 2-3 | 33-16-15 | L00652 | | 3 | 1A | | | | SM00012 | | W | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 21

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0035 | 286T0035 | | | P3-1 F/O INSTR PNL-L (continued) | | | | | | | | | | | |
| 054Z | | | | CD | 0-0 | 33-16-15 | L00652 | DED | | | SM00012 | DED | | | ALL |
| 055 | 22 | | PQ | CE | 2-4 | 33-16-15 | L00653 | 3 | 1A | | SM00012 | | W | | ALL |
| 055Z | | | | CE | 0-0 | 33-16-15 | L00653 | DED | | | SM00012 | DED | | | ALL |
| 056 | 22 | | PQ | CF | 2-3 | 33-16-15 | L00658 | 3 | 1A | | SM00012 | | W | | ALL |
| 056Z | | | | CF | 0-0 | 33-16-15 | L00658 | DED | | | SM00012 | DED | | | ALL |
| 057 | 22 | | PA | | 2-4 | 33-16-15 | L00804 | 3 | 1A | | SM00001 | | W | | 150-199, 275-299 |
| 058 | 20 | | PQ | CH | 2-5 | 27-51-11 | S00601 | 3 | 1A | | D05309J | 4 | | | ALL |
| 058Z | | | | CH | 0-0 | 27-51-11 | S00601 | DED | | | D05309J | DED | | | ALL |
| 059 | 20 | | PQ | CI | 2-5 | 27-51-11 | S00601 | 5 | 1A | | D05309J | 6 | | | ALL |
| 059Z | | | | CI | 0-0 | 27-51-11 | S00601 | DED | | | D05309J | DED | | | ALL |
| 060 | 20 | | PQ | CJ | 2-5 | 27-51-11 | S00601 | 1 | 1A | | D05309J | 7 | | | ALL |
| 060Z | | | | CJ | 0-0 | 27-51-11 | S00601 | DED | | | D05309J | DED | | | ALL |
| 061 | 20 | | PQ | CK | 1-2 | 27-51-11 | S00601 | 6 | 1A | | SM00015 | | W | | ALL |
| 061Z | | | | CK | 0-0 | 27-51-11 | S00601 | DED | | | SM00015 | DED | | | ALL |
| 062 | 22 | | PQ | CL | 1-2 | 27-51-11 | D05309J | 5 | | | SM00015 | | W | | ALL |
| 062Z | | | | CL | 0-0 | 27-51-11 | D05309J | DED | | | SM00015 | DED | | | ALL |
| 063 | 20 | | PQ | CM | 1-2 | 27-51-11 | S00601 | 2 | 1A | | SM00015 | | W | | ALL |
| 063Z | | | | CM | 0-0 | 27-51-11 | S00601 | DED | | | SM00015 | DED | | | ALL |
| 064 | 20 | | PA | | 1-5 | 27-51-11 | S00601 | 8 | 1A | | D05305J | 33 | | | ALL |
| 065 | 24 | | PK | | 1-5 | 27-51-11 | S00601 | 9 | 1A | | D05305J | 34 | | | ALL |
| 066 | 22 | | PA | | 1-10 | 27-58-31 | L00660 | 2 | 1A | | D05305J | 20 | | | ALL |
| 067 | 18 | | PA | | 1-7 | 32-35-11 | S00605 | 5 | C | | D05305J | 21 | DL | | ALL |
| 068 | 18 | | PA | | 1-8 | 32-35-11 | S00605 | 4 | C | | D04515J | 3 | DL | | ALL |
| 069 | 22 | | PA | | 1-0 | 33-16-15 | D05305J | 16 | | | SM00001 | | W | | ALL |
| 070 | 18 | | PQ | CT | 1-8 | 32-35-11 | S00605 | 3 | C | | D04515J | 2 | DL | | ALL |
| 070Z | | | | CT | 0-0 | 32-35-11 | S00605 | DED | | | D04515J | DED | | | ALL |
| 071 | 18 | | PQ | CU | 1-8 | 32-35-11 | S00605 | 2 | C | | D04515J | 4 | DL | | ALL |
| 071Z | | | | CU | 0-0 | 32-35-11 | S00605 | DED | | | D04515J | DED | | | ALL |
| 072 | 22 | | PA | | 2-6 | 32-46-11 | L00663 | 2 | 1A | | D05305J | 26 | | | ALL |
| 073 | 24 | | PK | | 2-6 | 32-61-14 | L00654 | 2 | 1A | | D05305J | 27 | | | ALL |
| 074 | 24 | | PK | | 2-6 | 32-61-14 | L00652 | 2 | 1A | | D05305J | 28 | | | ALL |
| 075 | 24 | | PK | | 2-6 | 32-61-14 | L00653 | 2 | 1A | | D05305J | 29 | | | ALL |
| 076 | 24 | | PK | | 0-11 | 32-61-14 | SM00009 | | W | | D05305J | 30 | | | ALL |
| 077 | 24 | | PK | | 0-11 | 32-61-14 | SM00010 | | W | | D05305J | 31 | | | ALL |
| 079 | 20 | | PQ | DD | 2-6 | 27-81-11 | S00602 | 3 | 1A | | D05309J | 25 | | | ALL |
| 079Z | | | | DD | 0-0 | 27-81-11 | S00602 | DED | | | D05309J | DED | | | ALL |
| 080 | 20 | | PQ | DE | 2-6 | 27-81-11 | S00602 | 11 | 1A | | D05309J | 29 | | | ALL |
| 080Z | | | | DE | 0-0 | 27-81-11 | S00602 | DED | | | D05309J | DED | | | ALL |
| 081 | 20 | | PQ | DF | 1-2 | 27-81-11 | S00602 | 12 | 1A | | SM00017 | | W | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0030
 Page 22
 May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0035 | 286T0035 | | | P3-1 F/O INSTR PNL-L (continued) | | | | | | | | | | | | |
| 081Z | | | DF | 0-0 | 27-81-11 | S00602 | DED | | | | SM00017 | DED | | | ALL | |
| 082 | 20 | PQ | DG | 1-2 | 27-81-11 | S00602 | 2 | 1A | | | SM00017 | | W | | ALL | |
| 082Z | | | DG | 0-0 | 27-81-11 | S00602 | DED | | | | SM00017 | DED | | | ALL | |
| 083 | 22 | PQ | DH | 1-3 | 27-81-11 | D05309J | 27 | | | | SM00017 | | W | | ALL | |
| 083Z | | | DH | 0-0 | 27-81-11 | D05309J | DED | | | | SM00017 | DED | | | ALL | |
| 084 | 22 | PQ | DI | 2-6 | 27-81-11 | S00602 | 1 | 1A | | | D05309J | 31 | | | ALL | |
| 084Z | | | DI | 0-0 | 27-81-11 | S00602 | DED | | | | D05309J | DED | | | ALL | |
| 085 | 20 | PQ | DJ | 2-6 | 27-81-21 | S00602 | 9 | 1A | | | D05309J | 17 | | | ALL | |
| 085Z | | | DJ | 0-0 | 27-81-21 | S00602 | DED | | | | D05309J | DED | | | ALL | |
| 086 | 20 | PQ | DK | 2-0 | 27-81-21 | S00602 | 8 | 1A | | | SM00018 | | W | | ALL | |
| 086Z | | | DK | 0-0 | 27-81-21 | S00602 | DED | | | | SM00018 | DED | | | ALL | |
| 087 | 20 | PQ | DL | 2-0 | 27-81-21 | S00602 | 6 | 1A | | | SM00018 | | W | | ALL | |
| 087Z | | | DL | 0-0 | 27-81-21 | S00602 | DED | | | | SM00018 | DED | | | ALL | |
| 088 | 18 | PQ | DM | 1-2 | 27-81-21 | D05309J | 19 | DL | | | SM00018 | | W | | ALL | |
| 088Z | | | DM | 0-0 | 27-81-21 | D05309J | DED | | | | SM00018 | DED | | | ALL | |
| 089 | 20 | PQ | DN | 2-6 | 27-81-21 | S00602 | 5 | 1A | | | D05309J | 21 | | | ALL | |
| 089Z | | | DN | 0-0 | 27-81-21 | S00602 | DED | | | | D05309J | DED | | | ALL | |
| 090 | 20 | PQ | DO | 2-6 | 27-81-21 | S00602 | 7 | 1A | | | D05309J | 23 | | | ALL | |
| 090Z | | | DO | 0-0 | 27-81-21 | S00602 | DED | | | | D05309J | DED | | | ALL | |
| 091 | 22 | PA | | 1-5 | 27-88-11 | L00661 | 2 | 1A | | | D05305J | 36 | | | ALL | |
| 092R | 22 | PH | | 2-5 | 26-17-11 | L00680 | 2 | 1A | | | D04515J | 15 | | | ALL | |
| 093 | 22 | PQ | DR | 2-1 | 33-16-15 | L00657 | 6 | 1A | | | SM00008 | | W | | ALL | |
| 093Z | | | DR | 0-0 | 33-16-15 | L00657 | DED | | | | SM00008 | DED | | | ALL | |
| 094 | 18 | PA | | 1-10 | 33-13-13 | GDX0001 | A.. | E | | | SM00004 | | W | | ALL | |
| 097 | 18 | PQ | DV | 1-8 | 32-35-11 | S00605 | 1 | C | | | D04515J | 1 | DL | | ALL | |
| 097Z | | | DV | 0-0 | 32-35-11 | S00605 | DED | | | | D04515J | DED | | | ALL | |
| 098 | 18 | PA | | 0-11 | 33-13-13 | D05305J | 11 | DL | | | SM00003 | | W | | ALL | |
| 099 | 18 | PA | | 2-1 | 33-13-13 | D05305J | 13 | DL | | | GDX0001 | A.. | E | | ALL | |
| 101 | 22 | PA | | 2-5 | 34-22-36 | S00616 | 1NC | Z2 | | | D05305J | 37 | | | ALL | |
| 102 | 20 | PA | | 2-5 | 34-22-36 | S00616 | 1C | Z2 | | | D05305J | 38 | | | ALL | |
| 103 | 22 | PQ | EC | 2-5 | 34-22-36 | S00616 | 4NO | Z2 | | | D04515J | 18 | | | ALL | |
| 103Z | | | EC | 0-0 | 34-22-36 | S00616 | DED | | | | D04515J | DED | | | ALL | |
| 104 | 20 | PQ | ED | 2-5 | 34-22-36 | S00616 | 4C | Z2 | | | D04515J | 19 | | | ALL | |
| 104Z | | | ED | 0-0 | 34-22-36 | S00616 | DED | | | | D04515J | DED | | | ALL | |
| 105 | 22 | PQ | EE | 2-5 | 34-22-36 | S00616 | 3NO | Z2 | | | D05309J | 8 | | | ALL | |
| 105Z | | | EE | 0-0 | 34-22-36 | S00616 | DED | | | | D05309J | DED | | | ALL | |
| 106 | 20 | PQ | EF | 2-5 | 34-22-36 | S00616 | 3C | Z2 | | | D05309J | 9 | | | ALL | |
| 106Z | | | EF | 0-0 | 34-22-36 | S00616 | DED | | | | D05309J | DED | | | ALL | |
| 107 | 20 | PA | | 2-5 | 33-13-13 | D05305J | 39 | | | | L00698 | =P | B | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 23

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|---|-------|-------------|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0035 | 286T0035 | P3-1 F/O INSTR PNL-L (continued) | | | | | | | | | | | | | |
| 108 | 22 | PA | | | 2-5 | 31-31-26 | S00601 | 12 | 1A | | D05309J | 10 | | | ALL |
| 109 | 22 | PA | | | 2-5 | 31-31-26 | S00601 | 10 | 1A | | D05309J | 11 | | | ALL |
| 110 | 22 | PA | | | 1-5 | 31-31-26 | S00603 | 7 | 1A | | D05305J | 35 | | | ALL |
| 126 | 22 | PQ | FA | | 2-1 | 33-16-15 | L00657 | 4 | 1A | | SM00007 | | W | | ALL |
| 126Z | | | FA | | 0-0 | 33-16-15 | L00657 | | DED | | SM00007 | | DED | | ALL |
| 127 | 22 | PQ | FB | | 2-0 | 33-16-15 | L00654 | 6 | 1A | | SM00008 | | W | | ALL |
| 127Z | | | FB | | 0-0 | 33-16-15 | L00654 | | DED | | SM00008 | | DED | | ALL |
| 128 | 22 | PQ | FC | | 2-0 | 33-16-15 | L00654 | 4 | 1A | | SM00007 | | W | | ALL |
| 128Z | | | FC | | 0-0 | 33-16-15 | L00654 | | DED | | SM00007 | | DED | | ALL |
| 129 | 22 | PQ | FD | | 2-0 | 33-16-15 | L00652 | 4 | 1A | | SM00019 | | W | | ALL |
| 129Z | | | FD | | 0-0 | 33-16-15 | L00652 | | DED | | SM00019 | | DED | | ALL |
| 130 | 22 | PQ | FE | | 2-0 | 33-16-15 | L00652 | 6 | 1A | | SM00020 | | W | | ALL |
| 130Z | | | FE | | 0-0 | 33-16-15 | L00652 | | DED | | SM00020 | | DED | | ALL |
| 131 | 22 | PQ | FF | | 2-1 | 33-16-15 | L00653 | 4 | 1A | | SM00019 | | W | | ALL |
| 131Z | | | FF | | 0-0 | 33-16-15 | L00653 | | DED | | SM00019 | | DED | | ALL |
| 132 | 22 | PQ | FG | | 2-1 | 33-16-15 | L00653 | 6 | 1A | | SM00020 | | W | | ALL |
| 132Z | | | FG | | 0-0 | 33-16-15 | L00653 | | DED | | SM00020 | | DED | | ALL |
| 133 | 22 | PQ | FH | | 2-0 | 33-16-15 | L00658 | 4 | 1A | | SM00019 | | W | | ALL |
| 133Z | | | FH | | 0-0 | 33-16-15 | L00658 | | DED | | SM00019 | | DED | | ALL |
| 134 | 22 | PQ | FI | | 2-0 | 33-16-15 | L00658 | 6 | 1A | | SM00020 | | W | | ALL |
| 134Z | | | FI | | 0-0 | 33-16-15 | L00658 | | DED | | SM00020 | | DED | | ALL |
| 135 | 22 | PQ | FJ | | 1-3 | 33-16-15 | D05309J | 13 | | | SM00019 | | W | | ALL |
| 135Z | | | FJ | | 0-0 | 33-16-15 | D05309J | | DED | | SM00019 | | DED | | ALL |
| 136 | 22 | PQ | FK | | 2-0 | 33-16-15 | D05309J | 14 | | | SM00020 | | W | | ALL |
| 136Z | | | FK | | 0-0 | 33-16-15 | D05309J | | DED | | SM00020 | | DED | | ALL |
| 137 | 24 | PK | | | 2-4 | 32-61-14 | L00657 | 2 | 1A | | SM00009 | | W | | ALL |
| 138 | 24 | PK | | | 2-4 | 32-61-14 | L00657 | 5 | 1A | | SM00009 | | W | | ALL |
| 139 | 24 | PK | | | 2-3 | 32-61-14 | L00658 | 2 | 1A | | SM00010 | | W | | ALL |
| 140 | 24 | PK | | | 2-3 | 32-61-14 | L00658 | 5 | 1A | | SM00010 | | W | | ALL |
| 162 | 24 | PK | | | 2-6 | 32-71-11 | D05305J | 32 | | | L00804 | 2 | 1A | | 150-199, 275-299 |
| 501 | 22 | PA | | | 4-0 | 33-16-15 | L01110 | 1 | 1A | | D05305J | 40 | | | 050-099 |
| 502 | 22 | PA | | | 4-0 | 33-16-15 | L01110 | 3 | 1A | | SM00001 | | W | | 050-099 |
| W0036 | 286T0036 | P11-L1-BUS DISTRIBUTION | | | | | | | | | | | | | |
| 001 | 12 | PA | | | 5-0 | 24-51-11 | TB5020 | 1 | E | * | C01432 | 2 | D | * | ALL |
| 002 | 12 | PA | | | 1-0 | 24-51-11 | C01432 | 2 | D | * | C01430 | 2 | D | | ALL |
| 003 | 12 | PA | | | 5-0 | 24-51-11 | TB5020 | 2 | E | * | C01439 | 2 | D | * | ALL |
| 004 | 12 | PA | | | 4-0 | 24-51-11 | C01439 | 2 | D | * | C01464 | 2 | D | | ALL |
| 005 | 12 | PA | | | 5-0 | 24-51-11 | TB5020 | 1 | E | * | C04280 | 2 | D | * | ALL |

WIRE LIST
D280T132

91-21-11
Section W0030
Page 24
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|-----------------------|--|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0036 | 286T0036 | | | P11-L1-BUS DISTRIBUTION (continued) | | | | | | | | | | | | |
| 006 | 12 | | PA | 5-0 | 24-51-11 | TB5020 | 2 | E | * | C00709 | 1 | D | * | ALL | | |
| 007 | 12 | | PA | 2-0 | 24-51-11 | C00709 | 1 | D | * | C04038 | 1 | D | * | ALL | | |
| 008 | 12 | | PA | 3-0 | 24-51-11 | C04038 | 1 | D | * | C00673 | 1 | D | * | ALL | | |
| 009 | 12 | | PA | 2-0 | 24-51-11 | C00673 | 1 | D | * | C01226 | 1 | D | * | 050-099 | | |
| 009 | 12 | | PA | 2-0 | 24-51-11 | C01312 | 1 | D | * | C01247 | 1 | D | * | 150-199 | | |
| 009 | 12 | | PA | 2-0 | 24-51-11 | C00673 | 1 | D | * | C01312 | 1 | D | * | 275-299 | | |
| 010 | 12 | | PA | 2-0 | 24-51-11 | C01226 | 1 | D | * | C01247 | 1 | D | * | 050-099 | | |
| 010 | 12 | | PA | 2-0 | 24-51-11 | C00668 | 1 | D | * | C04226 | 2 | D | * | 150-154 | | |
| 010 | 12 | | PA | 2-0 | 24-51-11 | C00668 | 1 | D | * | C04226 | 2 | D | * | 155-199 | | |
| 010 | 12 | | PA | 3-0 | 24-51-11 | C01312 | 1 | D | * | C01247 | 1 | D | * | 275-299 | | |
| 011 | 12 | | PA | 2-0 | 24-51-11 | C01247 | 1 | D | * | C00651 | 2 | D | * | ALL | | |
| 013 | 12 | | PA | 2-0 | 24-51-11 | C01313 | 1 | D | * | C01248 | 1 | D | * | ALL | | |
| 014 | 12 | | PA | 3-0 | 24-51-11 | C01248 | 1 | D | * | C00667 | 1 | D | * | ALL | | |
| 015 | 12 | | PA | 3-0 | 24-51-11 | C00520 | 2 | D | * | C04221 | 2 | D | * | 150-199, 275-299 | | |
| 016 | 12 | | PA | 5-0 | 24-51-11 | C01118 | 1 | D | * | C04226 | 2 | D | * | 050-099, 155-199 | | |
| 016 | 12 | | PA | 8-0 | 24-51-11 | C04226 | 2 | D | * | C01118 | 1 | D | * | 150-154 | | |
| 017 | 12 | | PA | 2-0 | 24-51-11 | C00847 | 1 | D | * | C01316 | 1 | D | * | ALL | | |
| 019 | 12 | | PA | 2-0 | 24-51-11 | C00667 | 1 | D | * | C01337 | 2 | D | * | ALL | | |
| 020 | 12 | | PA | 2-0 | 24-51-11 | C01337 | 2 | D | * | C04221 | 2 | D | * | ALL | | |
| 021 | 12 | | PA | 4-0 | 24-51-11 | C04221 | 2 | D | * | C00520 | 2 | D | * | 050-099 | | |
| 022 | 16 | | PA | 5-0 | 24-51-11 | TB5020 | 4 | E | * | C00513 | 1 | D | * | 050-099, 275-299 | | |
| 022 | 16 | | PA | 5-0 | 24-51-11 | TB5020 | 4 | E | * | C00513 | 1 | D | * | 150-199 | | |
| 023 | 16 | | PA | 2-0 | 24-51-11 | C00513 | 1 | D | * | C00628 | 2 | D | * | 150-199 | | |
| 024 | 16 | | PA | 2-0 | 24-51-11 | C00607 | 2 | D | * | C00592 | 2 | D | * | 150-199 | | |
| 025 | 16 | | PA | 3-0 | 24-51-11 | C00628 | 2 | D | * | C00607 | 2 | D | * | 050-099, 277-278 | | |
| 025 | 16 | | PA | 6-0 | 24-51-11 | TB5020 | 5 | E | * | C00616 | 2 | D | * | 150, 153-199 | | |
| 025 | 16 | | PA | 6-0 | 24-51-11 | TB5020 | 5 | E | * | C00607 | 2 | D | * | 151-152 | | |
| 025 | 16 | | PA | 6-0 | 24-51-11 | TB5020 | 5 | E | * | C00607 | 2 | D | * | 275-276 | | |
| 025 | 16 | | PA | 2-0 | 24-51-11 | C00628 | 2 | D | * | C00607 | 2 | D | * | 280-299 | | |
| 026 | 16 | | PA | 5-0 | 24-51-11 | TB5020 | 6 | E | * | C00501 | 2 | D | * | 050-099 | | |
| 026 | 16 | | PA | 6-0 | 24-51-11 | TB5020 | 6 | E | * | C00501 | 2 | D | * | 150-199, 275-299 | | |
| 027 | 16 | | PA | 3-0 | 24-51-11 | C00501 | 2 | D | * | C00615 | 2 | D | * | ALL | | |
| 029 | 12 | | PA | 6-0 | 24-51-11 | C04181 | 2 | D | * | TB5020 | 4 | E | * | 050-099 | | |
| 029 | 16 | | PA | 6-0 | 24-51-11 | C04181 | 2 | D | * | TB5020 | 4 | E | * | 150, 153-199, 277-299 | | |
| 029 | 16 | | PA | 6-0 | 24-51-11 | C04181 | 2 | D | * | TB5020 | 4 | E | * | 151-152, 275-276 | | |
| 030 | 16 | | PA | 5-0 | 24-51-11 | TB5020 | 5 | E | * | C01536 | 1 | D | * | 050-099, 275-299 | | |
| 030 | 16 | | PA | 5-0 | 24-51-11 | TB5020 | 5 | E | * | C01536 | 1 | D | * | 150-199 | | |
| 031 | 16 | | PA | 2-0 | 24-51-11 | C01536 | 1 | D | * | C00559 | 1 | D | * | 050-099 | | |
| 031 | 16 | | PA | 3-0 | 24-51-11 | C01536 | 1 | D | * | C00559 | 1 | D | * | 150-199 | | |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 25

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0036 | 286T0036 | | | P11-L1-BUS DISTRIBUTION (continued) | | | | | | | | | | | |
| 031 | 16 | | PA | | 3-0 | 24-51-11 | C00559 | 1 | D | | C01536 | 1 | D | * | 275-299 |
| 032 | 16 | | PA | | 3-0 | 24-51-11 | C04181 | 2 | D | * | C00506 | 2 | D | * | 150, 153-199 |
| 032 | 16 | | PA | | 4-0 | 24-51-11 | C04181 | 2 | D | * | C00506 | 2 | D | | 277-278 |
| 032 | 16 | | PA | | 2-0 | 24-51-11 | C04181 | 2 | D | * | C00506 | 2 | D | | 280-299 |
| 033 | 16 | | PA | | 5-0 | 24-51-11 | TB5020 | 6 | E | * | C00561 | 1 | D | * | 050-099 |
| 033 | 16 | | PA | | 5-0 | 24-51-11 | TB5020 | 6 | E | | C00561 | 1 | D | * | 150-199, 275-299 |
| 034 | 16 | | PA | | 2-0 | 24-51-11 | C00561 | 1 | D | * | C04081 | 1 | D | | ALL |
| 036 | 12 | | PA | | 6-0 | 24-51-42 | TB5020 | 12 | E | * | C01237 | 2 | D | | ALL |
| 040 | 12 | | PA | | 2-0 | 24-51-42 | C00633 | 1 | D | * | C00580 | 1 | D | | 050-099 |
| 040 | 12 | | PA | | 2-0 | 24-51-42 | C00593 | 1 | D | | C00580 | 1 | D | | 150-199 |
| 040 | 12 | | PA | | 2-0 | 24-51-42 | C00580 | 1 | D | | C00593 | 1 | D | | 280-299 |
| 041 | 14 | | PA | | 6-0 | 24-53-11 | TB5020 | 9 | E | * | C01252 | 2 | D | | ALL |
| 044 | 14 | | PA | | 5-0 | 24-53-11 | TB5020 | 9 | E | * | C01524 | 1 | D | * | ALL |
| 045 | 14 | | PA | | 2-0 | 24-53-11 | C01524 | 1 | D | * | C01002 | 2 | D | * | ALL |
| 046 | 14 | | PA | | 3-0 | 24-53-11 | C01002 | 2 | D | * | C01523 | 1 | D | * | ALL |
| 047 | 14 | | PA | | 3-0 | 24-53-11 | C01523 | 1 | D | * | C00672 | 1 | D | * | ALL |
| 048 | 14 | | PA | | 2-0 | 24-53-11 | C00672 | 1 | D | * | C04099 | 2 | D | * | 050-099, 275-299 |
| 048 | 14 | | PA | | 3-0 | 24-53-11 | C00672 | 1 | D | * | C04099 | 2 | D | * | 150-199 |
| 049 | 14 | | PA | | 1-0 | 24-53-11 | C04099 | 2 | D | * | C01005 | 2 | D | * | ALL |
| 050 | 14 | | PA | | 2-0 | 24-53-11 | C01005 | 2 | D | * | C01082 | 1 | D | * | ALL |
| 051 | 14 | | PA | | 2-0 | 24-53-11 | C01082 | 1 | D | * | C01498 | 1 | D | * | ALL |
| 052 | 08 | | PA | | 5-0 | 24-54-11 | TB5020 | 8 | E | | C01054 | 2 | LA | * | ALL |
| 053 | 08 | | PA | | 2-0 | 24-54-11 | C01054 | 2 | LA | * | C01412 | 2 | LA | * | 050-099, 150-154, 275 |
| 054 | 08 | | PA | | 2-0 | 24-54-11 | C01412 | 2 | LA | * | C01458 | 2 | LA | * | 050-099, 150-154, 275 |
| 054 | 08 | | PA | | 2-0 | 24-54-11 | C01054 | 2 | LA | * | C01458 | 2 | LA | * | 155-199, 276-299 |
| 055 | 08 | | PA | | 1-0 | 24-54-11 | C01458 | 2 | LA | * | C01466 | 1 | LA | * | 050-099, 277-278 |
| 055 | 08 | | PA | | 1-0 | 24-54-11 | C01458 | 2 | LA | * | C01465 | 1 | LA | * | 150-199 |
| 055 | 08 | | PA | | 1-0 | 24-54-11 | C01458 | 2 | LA | * | C01460 | 1 | LA | * | 275-276 |
| 055 | 08 | | PA | | 2-0 | 24-54-11 | C01458 | 2 | LA | * | C01460 | 1 | LA | * | 280-299 |
| 056 | 08 | | PA | | 1-0 | 24-54-11 | C01090 | 1 | D | * | C01095 | 1 | D | | 050-099 |
| 056 | 08 | | PA | | 1-0 | 24-54-11 | C01090 | 1 | LA | * | C01095 | 1 | D | | 150-199, 275-299 |
| 058 | 08 | | PA | | 5-0 | 24-54-11 | TB5020 | 8 | E | | C04039 | 1 | LA | | 050-099 |
| 058 | 08 | | PA | | 5-0 | 24-54-11 | TB5020 | 8 | E | | C04039 | 1 | / | * | 150-156, 162-166 |
| 058 | 08 | | PA | | 5-0 | 24-54-11 | TB5020 | 8 | E | | C04039 | 1 | LA | * | 157, 167-199, 275-299 |
| 059 | 08 | | PA | | 2-0 | 24-54-11 | C04039 | 1 | / | | C00702 | 1 | / | | 050-099 |
| 059 | 08 | | PA | | 2-0 | 24-54-11 | C04039 | 1 | / | * | C00702 | 1 | / | | 150-156, 162-166 |
| 059 | 08 | | PA | | 2-0 | 24-54-11 | C04039 | 1 | LA | * | C00702 | 1 | LA | * | 157, 167-199, 276-299 |
| 059 | 08 | | PA | | 2-0 | 24-54-11 | C04039 | 1 | / | * | C00702 | 1 | / | * | 275 |

WIRE LIST
D280T132

91-21-11
Section W0030
Page 26
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|--------|--------|-------------|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0036 | 286T0036 | | | P11-L1-BUS DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 060 | 08 | PA | | 2-0 | 24-54-11 | C00702 | | 1 | LA | | | | C01259 | 1 | LA | * | 050-099, 150-156, 162-166 |
| 060 | 08 | PA | | 2-0 | 24-54-11 | C00702 | | 1 | LA | * | | | C01259 | 1 | LA | * | 157, 167-199, 275-299 |
| 061 | 08 | PA | | 2-0 | 24-54-11 | C01259 | | 1 | LA | * | | | C00654 | 2 | LA | * | ALL |
| 064 | 08 | PA | | 2-0 | 24-54-11 | C00654 | | 2 | LA | * | | | C04019 | 1 | LA | * | ALL |
| 065 | 08 | PA | | 1-0 | 24-54-11 | C04019 | | 1 | LA | * | | | C00660 | 1 | LA | * | ALL |
| 066 | 08 | PA | | 2-0 | 24-54-11 | C00660 | | 1 | LA | * | | | C01367 | 1 | LA | * | ALL |
| 067 | 08 | PA | | 3-0 | 24-54-11 | C01309 | | 1 | LA | * | | | C01371 | 1 | LA | * | 050-099 |
| 067 | 08 | PA | | 2-0 | 24-54-11 | C01371 | | 1 | LA | * | | | C01309 | 1 | LA | * | 150-199, 275-299 |
| 068 | 08 | PA | | 1-0 | 24-54-11 | C01309 | | 1 | LA | * | | | C01298 | 1 | LA | * | ALL |
| 069 | 08 | PA | | 2-0 | 24-54-11 | C01343 | | 2 | LA | * | | | C01298 | 1 | LA | * | ALL |
| 070 | 08 | PA | | 2-0 | 24-54-11 | C01343 | | 2 | LA | * | | | C01338 | 2 | LA | * | ALL |
| 071 | 08 | PA | | 3-0 | 24-54-11 | C01338 | | 2 | LA | * | | | C01171 | 2 | LA | * | 050-099 |
| 071 | 08 | PA | | 3-0 | 24-54-11 | C01338 | | 2 | LA | * | | | C01143 | 1 | LA | * | 150-199, 275-299 |
| 072 | 08 | PA | | 2-0 | 24-54-11 | C00822 | | 1 | D | | | | C01143 | 1 | LA | * | 050-099 |
| 072 | 08 | PA | | 2-0 | 24-54-11 | C01143 | | 1 | LA | * | | | C00822 | 1 | LA | * | 150-199, 275-299 |
| 073 | 08 | PA | | 1-0 | 24-54-11 | C01181 | | 2 | LA | * | | | C01186 | 2 | LA | * | 050-099 |
| 074 | 08 | PA | | 2-0 | 24-54-11 | C00737 | | 2 | LA | * | | | C01176 | 2 | LA | * | 050-099, 150-199, 275-276 |
| 074 | 08 | PA | | 2-0 | 24-54-11 | C00741 | | 2 | LA | * | | | C01176 | 2 | LA | * | 277-299 |
| 075 | 08 | PA | | 1-0 | 24-54-11 | C01176 | | 2 | LA | * | | | C01177 | 2 | LA | * | ALL |
| 076 | 08 | PA | | 2-0 | 24-54-11 | C01182 | | 2 | LA | * | | | C01181 | 2 | LA | * | 050-099 |
| 076 | 08 | PA | | 1-0 | 24-54-11 | C01186 | | 2 | LA | * | | | C01171 | 2 | D | | 150-199 |
| 076 | 08 | PA | | 1-0 | 24-54-11 | C01171 | | 2 | D | | | | C01186 | 2 | LA | * | 275-299 |
| 077 | 10 | PA | | 5-0 | 24-54-11 | TB5020 | | 7 | E | * | | | C00522 | 1 | D | * | ALL |
| 078 | 10 | PA | | 1-0 | 24-54-11 | C00522 | | 1 | D | * | | | C00516 | 1 | D | * | ALL |
| 080 | 10 | PA | | 5-0 | 24-54-11 | TB5020 | | 7 | E | * | | | C01035 | 2 | D | * | ALL |
| 082 | 10 | PA | | 2-0 | 24-54-11 | C01035 | | 2 | D | * | | | C01449 | 2 | D | * | ALL |
| 083 | 10 | PA | | 1-0 | 24-54-11 | C01449 | | 2 | D | * | | | C00578 | 1 | D | * | 050-099, 150-199 |
| 083 | 10 | PA | | 2-0 | 24-54-11 | C01449 | | 2 | D | * | | | C00578 | 1 | D | * | 275-299 |
| 084 | 10 | PA | | 2-0 | 24-54-11 | C00578 | | 1 | D | * | | | C01022 | 1 | D | * | 050-099 |
| 084 | 10 | PA | | 2-0 | 24-54-11 | C01017 | | 2 | D | * | | | C04027 | 2 | D | * | 150-199 |
| 085 | 10 | PA | | 2-0 | 24-54-11 | C01022 | | 1 | D | * | | | C01013 | 2 | D | * | ALL |
| 086 | 10 | PA | | 2-0 | 24-54-11 | C01013 | | 2 | D | * | | | C01017 | 2 | D | * | ALL |
| 087 | 10 | PA | | 2-0 | 24-54-11 | C04027 | | 2 | D | * | | | C00539 | 1 | D | * | 050-099, 150-199 |
| 087 | 10 | PA | | 2-0 | 24-54-11 | C04026 | | 2 | D | * | | | C00539 | 1 | D | * | 275-299 |
| 088 | 10 | PA | | 2-0 | 24-54-11 | C00539 | | 1 | D | * | | | C01023 | 1 | D | * | ALL |
| 089 | 10 | PA | | 2-0 | 24-54-11 | C01023 | | 1 | D | * | | | C01531 | 1 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 27

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|--------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0036 | 286T0036 | | | P11-L1-BUS DISTRIBUTION (continued) | | | | | | | | | | | |
| 094 | 08 | PA | | | 2-0 | 24-54-11 | C01090 | 1 | LA | * | C01460 | 1 | LA | * | 050-099, 150-199, 277-278 |
| 094 | 08 | PA | | | 2-0 | 24-54-11 | C01090 | 1 | LA | * | C01466 | 1 | LA | * | 275-276, 280-299 |
| 115 | 12 | PA | | | 5-0 | 24-51-11 | C01313 | 1 | D | * | TB5020 | 3 | E | | 050-099 |
| 115 | 12 | PA | | | 4-0 | 24-51-11 | C01313 | 1 | D | * | TB5020 | 3 | E | | 150-199 |
| 115 | 12 | PA | | | 5-0 | 24-51-11 | TB5020 | 3 | E | | C01313 | 1 | D | * | 275-299 |
| 116 | 14 | PA | | | 1-0 | 24-53-11 | C01415 | 2 | D | | C01498 | 1 | D | * | 050-099 |
| 116 | 14 | PA | | | 2-0 | 24-53-11 | C01415 | 2 | D | | C01498 | 1 | D | * | 150-199, 275-299 |
| 117 | 12 | PA | | | 3-0 | 24-51-11 | C01316 | 1 | D | * | C00651 | 2 | D | * | ALL |
| 118 | 08 | PA | | | 2-0 | 24-54-11 | C00822 | 1 | LA | * | C00737 | 2 | LA | * | 150-199, 275-276 |
| 118 | 08 | PA | | | 2-0 | 24-54-11 | C00822 | 1 | LA | * | C00742 | 2 | LA | * | 277-299 |
| 119 | 10 | PA | | | 2-0 | 24-54-11 | C00516 | 1 | D | * | C00512 | 2 | D | * | 050-099, 157, 167-199, 275-299 |
| 119 | 10 | PA | | | 2-0 | 24-54-11 | C00516 | 1 | D | * | C00512 | 2 | D | | 150-156, 162-166 |
| 120 | 10 | PA | | | 2-0 | 24-54-11 | C04423 | 2 | D | | C00512 | 2 | D | * | 050-099, 275-299 |
| 122 | 12 | PA | | | 4-0 | 24-51-11 | C00520 | 2 | D | * | C04230 | 2 | D | * | ALL |
| 123 | 12 | PA | | | 2-0 | 24-51-11 | C04280 | 2 | D | * | C01244 | 2 | D | * | 050-099, 150-199 |
| 123 | 12 | PA | | | 4-0 | 24-51-11 | C00668 | 1 | D | * | C01244 | 2 | D | * | 275-299 |
| 125 | 16 | PA | | | 1-0 | 24-51-11 | C00607 | 2 | D | * | C00592 | 2 | D | | 050-099, 275-278 |
| 125 | 16 | PA | | | 1-0 | 24-51-11 | C00607 | 2 | D | * | C00616 | 2 | D | * | 150, 153-199 |
| 125 | 16 | PA | | | 2-0 | 24-51-11 | C00607 | 2 | D | * | C00592 | 2 | D | | 280-299 |
| 126 | 12 | PA | | | 7-0 | 24-51-42 | C00633 | 1 | D | * | TB5152 | 9 | E | | 050-099 |
| 126 | 12 | PA | | | 7-0 | 24-51-42 | C00633 | 1 | D | | TB5152 | 9 | E | | 150-199, 275-299 |
| 127 | 12 | PA | | | 6-0 | 24-51-42 | C00603 | 1 | D | * | TB5020 | 12 | E | * | ALL |
| 129 | 12 | PA | | | 1-0 | 24-51-42 | C00588 | 1 | D | | C00600 | 2 | D | * | ALL |
| 130 | 12 | PA | | | 1-0 | 24-51-42 | C00600 | 2 | D | * | C00639 | 2 | D | * | ALL |
| 131 | 12 | PA | | | 7-0 | 24-51-42 | C00639 | 2 | D | * | TB5152 | 8 | E | | ALL |
| 132 | 20 | PA | | | 8-0 | 24-51-43 | C04230 | 1 | D | | TB0292F | C002 | 2 | | ALL |
| 133 | 20 | PA | | | 8-0 | 24-51-43 | C04226 | 1 | D | | TB0292F | C003 | 2 | | ALL |
| 134 | 20 | PA | | | 8-0 | 24-51-43 | C04228 | 1 | D | | TB0292F | C004 | 2 | | ALL |
| 135 | 12 | PA | | | 1-0 | 24-51-42 | C00637 | 2 | D | | C00603 | 1 | D | * | ALL |
| 137 | 12 | PA | | | 7-0 | 24-51-14 | C00340 | A1 | D | | TB5152 | 1 | E | * | 050-099 |
| 137 | 12 | PA | | | 7-0 | 24-51-14 | C00340 | A1 | D | | TB5152 | 1 | E | | 150-199, 275-299 |
| 138 | 12 | PA | | | 7-0 | 24-51-14 | C00340 | B1 | D | | TB5152 | 10 | E | * | 050-099, 150-199 |
| 138 | 12 | PA | | | 7-0 | 24-51-14 | C00340 | B1 | D | | TB5152 | 10 | E | | 275-299 |
| 139 | 12 | PA | | | 7-0 | 24-51-14 | C00340 | C1 | D | | TB5152 | 3 | E | * | 050-099 |
| 139 | 12 | PA | | | 7-0 | 24-51-14 | C00340 | C1 | D | | TB5152 | 3 | E | | 150-199, 275-299 |
| 141 | 08 | PA | | | 1-0 | 24-54-11 | C01177 | 2 | LA | * | C01182 | 2 | LA | * | 050-099 |
| 143 | 08 | PA | | | 2-0 | 24-54-11 | C01128 | 1 | LA | * | C00737 | 2 | LA | * | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0030
Page 28
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0036 | 286T0036 | | | P11-L1-BUS DISTRIBUTION (continued) | | | | | | | | | | | | |
| 143 | 08 | PA | | 1-0 | 24-54-11 | C00742 | 2 | LA | * | C00741 | 2 | LA | * | 277-278 | | |
| 143 | 08 | PA | | 2-0 | 24-54-11 | C00742 | 2 | LA | * | C00741 | 2 | LA | * | 280-299 | | |
| 146 | 12 | PA | | 2-0 | 24-51-11 | C04230 | 2 | D | * | C01232 | 2 | D | | 050-099 | | |
| 146 | 12 | PA | | 2-0 | 24-51-11 | C01232 | 2 | D | | C04230 | 2 | D | * | 150-199, 275-299 | | |
| 147 | 12 | PA | | 2-0 | 24-51-11 | C00847 | 1 | D | * | C04228 | 2 | D | | 050-099 | | |
| 147 | 12 | PA | | 2-0 | 24-51-11 | C04228 | 2 | D | | C00847 | 1 | D | * | 150-199, 275-299 | | |
| 148 | 12 | PA | | 7-0 | 24-51-14 | C00582 | 1 | D | * | TB5152 | 1 | E | * | 050-099 | | |
| 148 | 12 | PA | | 7-0 | 24-51-14 | C00582 | 1 | D | * | TB5152 | 1 | E | | 150-199, 275-299 | | |
| 149 | 12 | PA | | 1-0 | 24-51-14 | C00582 | 1 | D | * | C00609 | 1 | D | | 050-099 | | |
| 149 | 12 | PA | | 1-0 | 24-51-14 | C00582 | 1 | D | * | C00597 | 1 | D | | 150-199, 275-299 | | |
| 150 | 12 | PA | | 7-0 | 24-51-14 | C00611 | 2 | D | | TB5152 | 3 | E | * | ALL | | |
| 151 | 18 | PA | | 2-0 | 24-51-14 | C01008 | 1 | D | | C01034 | 2 | D | * | ALL | | |
| 152 | 18 | PA | | 5-0 | 24-51-14 | TB5152 | 2 | E | * | C01034 | 2 | D | * | 050-099 | | |
| 152 | 18 | PA | | 5-0 | 24-51-14 | C01034 | 2 | D | * | TB5152 | 2 | E | * | 150-199, 275-299 | | |
| 153 | 18 | PA | | 7-0 | 24-51-14 | C01318 | 1 | D | | TB5152 | 2 | E | * | ALL | | |
| 154 | 12 | PA | | 4-0 | 24-51-14 | C01330 | 2 | D | | C01242 | 2 | D | * | ALL | | |
| 155 | 12 | PA | | 2-0 | 24-51-14 | C01241 | 2 | D | * | C01242 | 2 | D | * | 050-099 | | |
| 155 | 12 | PA | | 2-0 | 24-51-14 | C01242 | 2 | D | * | C01241 | 2 | D | * | 150-199, 275-299 | | |
| 156 | 12 | PA | | 7-0 | 24-51-14 | C01241 | 2 | D | * | TB5152 | 3 | E | * | ALL | | |
| 160 | 08 | PA | | 1-0 | 24-54-11 | C01177 | 2 | LA | * | C01182 | 2 | LA | * | 150-199, 275-299 | | |
| 161 | 08 | PA | | 1-0 | 24-54-11 | C01182 | 2 | LA | * | C01181 | 2 | LA | * | 150-199, 275-299 | | |
| 162 | 08 | PA | | 1-0 | 24-54-11 | C01181 | 2 | LA | * | C01186 | 2 | LA | * | 150-199, 275-299 | | |
| 163 | 10 | PA | | 2-0 | 24-54-11 | C00578 | 1 | D | * | C01022 | 1 | D | * | 150-199, 275-299 | | |
| 164 | 12 | PA | | 6-0 | 24-51-14 | C00686 | 2 | D | * | TB5152 | 10 | E | * | 050-099 | | |
| 164 | 12 | PA | | 6-0 | 24-51-14 | TB5152 | 10 | E | * | C00686 | 2 | D | * | 150-199 | | |
| 164 | 12 | PA | | 6-0 | 24-51-14 | TB5152 | 10 | E | | C00686 | 2 | D | * | 275-299 | | |
| 165 | 12 | PA | | 3-0 | 24-51-14 | C00686 | 2 | D | * | C01289 | 2 | D | | ALL | | |
| 166 | 12 | PA | | 4-0 | 24-51-11 | C01244 | 2 | D | * | C00668 | 1 | D | * | 050-099, 150-199 | | |
| 166 | 12 | PA | | 4-0 | 24-51-11 | C01244 | 2 | D | * | C04226 | 2 | D | | 275-299 | | |
| 174 | 12 | PA | | 3-0 | 24-51-11 | C01312 | 1 | D | * | C00673 | 1 | D | * | 150-199 | | |
| 175 | 08 | PA | | 2-0 | 24-54-11 | C01367 | 1 | LA | * | C01371 | 1 | LA | * | ALL | | |
| 185 | 12 | PA | | 6-0 | 24-51-14 | TB5152 | 10 | E | | C00616 | 2 | D | | 050-099, 150-155, 162-165, 275-276 | | |
| 185 | 12 | PA | | 7-0 | 24-51-14 | C00616 | 2 | D | | TB5152 | 10 | E | | 156-157, 166-199, 277-299 | | |
| 187 | 10 | PA | | 2-0 | 24-54-11 | C04027 | 2 | D | * | C01017 | 2 | D | * | 050-099 | | |
| 187 | 10 | PA | | 2-0 | 24-54-11 | C04026 | 2 | D | * | C01017 | 2 | D | * | 275-299 | | |
| 188 | 08 | PA | | 1-0 | 24-54-11 | C01186 | 2 | LA | * | C01171 | 2 | LA | * | 050-099 | | |
| 195 | 12 | PA | | 1-0 | 24-51-11 | C04226 | 2 | D | * | C00668 | 1 | D | * | 050-099 | | |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 29

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0036 | 286T0036 | | | P11-L1-BUS DISTRIBUTION (continued) | | | | | | | | | | | |
| 195 | 12 | | PA | | 4-0 | 24-51-11 | C00668 | 1 | D | * | C04280 | 2 | D | * | 275-299 |
| 196 | 10 | | PA | | 4-0 | 24-54-11 | C04423 | 2 | D | | C00512 | 2 | D | | 150-154 |
| 196 | 10 | | PA | | 5-0 | 24-54-11 | C00512 | 2 | D | | C04423 | 2 | D | | 155 |
| 196 | 10 | | PA | | 2-0 | 24-54-11 | C04423 | 2 | D | | C00512 | 2 | D | * | 156-157 |
| 196 | 10 | | PA | | 2-0 | 24-54-11 | C00512 | 2 | D | | C04423 | 2 | D | | 162-199 |
| 197 | 08 | | PA | | 1-0 | 24-54-11 | C01128 | 1 | LA | * | C01143 | 1 | LA | * | 050-099 |
| 198 | 16 | | PA | | 6-0 | 24-51-11 | C00628 | 2 | D | * | TB5020 | 5 | E | * | 050-099, 277-299 |
| 199 | 08 | | PA | | 1-0 | 24-54-11 | C01460 | 1 | LA | * | C01466 | 1 | LA | * | 050-099 |
| 199 | 08 | | PA | | 4-0 | 24-54-11 | C01460 | 1 | LA | * | C01465 | 1 | LA | * | 150-154 |
| 199 | 08 | | PA | | 2-0 | 24-54-11 | C01460 | 1 | LA | * | C01465 | 1 | LA | * | 155-199 |
| 199 | 08 | | PA | | 1-0 | 24-54-11 | C01466 | 1 | LA | * | C01460 | 1 | LA | * | 275-276 |
| 199 | 08 | | PA | | 2-0 | 24-54-11 | C01466 | 1 | LA | * | C01460 | 1 | LA | * | 277-278 |
| 199 | 08 | | PA | | 2-0 | 24-54-11 | C01460 | 1 | LA | * | C01466 | 1 | LA | * | 280-299 |
| 504 | 08 | | PA | | 1-0 | 24-54-11 | C01128 | 1 | D | | C01136 | 1 | D | | 155-199 |
| 901 | 16 | | PA | | 2-0 | 24-54-11 | C04027 | 2 | D | * | C00724 | 2 | D | * | 150, 153-155, 162-165 |
| 902 | 16 | | PA | | 2-0 | 24-54-11 | C00724 | 2 | D | * | C00901 | 2 | D | | 150, 153-155, 162-165 |
| 904 | 16 | | PA | | 2-0 | 24-54-11 | C00724 | 2 | D | | C00901 | 2 | D | | 156-157, 166-199 |
| 907 | 16 | | PA | | 3-0 | 24-51-11 | C00902 | 2 | D | | C00506 | 2 | D | * | 156-157, 166-199 |
| 909 | 16 | | PA | | 3-0 | 24-51-11 | C00902 | 2 | D | | C00506 | 2 | D | * | 150, 153-155, 162-165 |
| 910 | 10 | | PA | | 3-0 | 24-54-11 | C09007 | 2 | D | | C04423 | 2 | D | | 150, 152-199, 275-299 |
| W0038 | 286T0038 | | | P11-R1-BUS DISTRIBUTION | | | | | | | | | | | |
| 001 | 12 | | PA | | 6-0 | 24-51-21 | TB5022 | 2 | E | * | C01431 | 2 | D | * | ALL |
| 002 | 12 | | PA | | 2-0 | 24-51-21 | C01431 | 2 | D | * | C01440 | 2 | D | | ALL |
| 003 | 12 | | PA | | 5-0 | 24-51-21 | TB5022 | 2 | E | * | C00674 | 1 | D | * | ALL |
| 004 | 12 | | PA | | 2-0 | 24-51-21 | C00674 | 1 | D | * | C04036 | 1 | D | * | 050-099 |
| 004 | 12 | | PA | | 2-0 | 24-51-21 | C00674 | 1 | D | * | C04180 | 1 | D | * | 150-199, 275-299 |
| 005 | 12 | | PA | | 3-0 | 24-51-21 | C04036 | 1 | D | * | C01336 | 2 | D | * | ALL |
| 008 | 12 | | PA | | 5-0 | 24-51-21 | C04231 | 2 | D | * | C01119 | 1 | D | | 050-099 |
| 008 | 12 | | PA | | 5-0 | 24-51-21 | C04231 | 2 | D | | C01119 | 1 | D | | 150-154 |
| 008 | 12 | | PA | | 5-0 | 24-51-21 | C01119 | 1 | D | | C04231 | 2 | D | * | 155-199 |
| 009 | 12 | | PA | | 5-0 | 24-51-21 | TB5022 | 4 | E | | C04231 | 2 | D | * | 050-099, 155-199 |
| 009 | 12 | | PA | | 6-0 | 24-51-21 | TB5022 | 4 | E | | C04231 | 2 | D | | 150-154, 275-299 |
| 010 | 12 | | PA | | 5-0 | 24-51-21 | TB5022 | 3 | E | | C01250 | 1 | D | * | ALL |
| 011 | 12 | | PA | | 2-0 | 24-51-21 | C01250 | 1 | D | * | C04180 | 1 | D | * | 050-099 |
| 011 | 12 | | PA | | 1-0 | 24-51-21 | C01250 | 1 | D | * | C01240 | 2 | D | * | 150-199, 275-299 |
| 012 | 12 | | PA | | 1-0 | 24-51-21 | C01240 | 2 | D | * | C04185 | 2 | D | * | ALL |
| 013 | 12 | | PA | | 3-0 | 24-51-21 | C04185 | 2 | D | * | C00848 | 1 | D | * | ALL |
| 015 | 12 | | PA | | 2-0 | 24-51-21 | C00848 | 1 | D | * | C01317 | 1 | D | * | ALL |

WIRE LIST
D280T132

91-21-11
Section W0030
Page 30
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|-------------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0038 | 286T0038 | | | P11-R1-BUS DISTRIBUTION (continued) | | | | | | | | | | | |
| 016 | 16 | PA | | | 6-0 | 24-51-21 | TB5022 | 5 | E | * | C00583 | 1 | D | | ALL |
| 018 | 12 | PA | | | 3-0 | 24-51-21 | C01336 | 2 | D | * | C04227 | 2 | D | | 150-199, 275-299 |
| 019 | 16 | PA | | | 5-0 | 24-51-21 | TB5022 | 6 | E | * | C00612 | 2 | D | * | 050-099 |
| 019 | 16 | PA | | | 6-0 | 24-51-21 | TB5022 | 6 | E | * | C00612 | 2 | D | * | 150-199, 275-299 |
| 020 | 16 | PA | | | 2-0 | 24-51-21 | C00612 | 2 | D | * | C00636 | 2 | D | * | ALL |
| 021 | 16 | PA | | | 6-0 | 24-51-21 | TB5022 | 7 | E | * | C00598 | 1 | D | * | ALL |
| 022 | 16 | PA | | | 2-0 | 24-51-21 | C00598 | 1 | D | * | C00514 | 1 | D | | 150-199, 275-299 |
| 023 | 16 | PA | | | 2-0 | 24-51-21 | C00598 | 1 | D | * | C00514 | 1 | D | | 050-099 |
| 024 | 16 | PA | | | 5-0 | 24-51-21 | TB5022 | 5 | E | * | C04079 | 1 | D | * | ALL |
| 025 | 16 | PA | | | 2-0 | 24-51-21 | C04079 | 1 | D | * | C00565 | 1 | D | * | ALL |
| 027 | 16 | PA | | | 4-0 | 24-51-21 | C00565 | 1 | D | * | C00341 | A1 | D | | ALL |
| 028 | 16 | PA | | | 5-0 | 24-51-21 | TB5022 | 6 | E | * | C01535 | 1 | D | * | 050-099 |
| 028 | 16 | PA | | | 5-0 | 24-51-21 | TB5022 | 6 | E | * | C01535 | 1 | D | * | 150-199, 275-299 |
| 029 | 16 | PA | | | 3-0 | 24-51-21 | C01535 | 1 | D | * | C00532 | 2 | D | * | ALL |
| 030 | 16 | PA | | | 2-0 | 24-51-21 | C00532 | 2 | D | * | C00341 | B1 | D | | ALL |
| 031 | 16 | PA | | | 6-0 | 24-51-21 | TB5022 | 7 | E | * | C00341 | C1 | D | | ALL |
| 032 | 22 | PQ | A | | 5-0 | 24-51-31 | TB5022 | 11 | E | | C00515 | 1 | D | * | ALL |
| 032Z | | | A | | 0-0 | 24-51-31 | TB5022 | DED | | | C00515 | DED | | | ALL |
| 033 | 22 | PQ | B | | 2-0 | 24-51-31 | C00515 | 1 | D | * | C00602 | 2 | D | | ALL |
| 033Z | | | B | | 0-0 | 24-51-31 | C00515 | DED | | | C00602 | DED | | | ALL |
| 034 | 18 | PQ | C | | 5-0 | 24-51-31 | TB5022 | 12 | E | | C00524 | 1 | D | | ALL |
| 034Z | | | C | | 0-0 | 24-51-31 | TB5022 | DED | | | C00524 | DED | | | ALL |
| 035 | 12 | PA | | | 5-6 | 24-51-52 | C00794 | 2 | D | * | C01192 | 2 | D | * | ALL |
| 036 | 12 | PA | | | 4-0 | 24-51-52 | C01192 | 2 | D | * | C01225 | 1 | D | | 050-099, 150-199, 277-299 |
| 036 | 12 | PA | | | 4-0 | 24-51-52 | C01192 | 2 | D | * | C01225 | 1 | D | * | 275-276 |
| 037 | 14 | PA | | | 5-0 | 24-51-52 | TB5022 | 1 | E | * | C01101 | 1 | D | * | 050-099, 155-199, 277-299 |
| 037 | 14 | PA | | | 5-0 | 24-51-52 | TB5022 | 1 | E | * | C01101 | 1 | D | | 150-154, 275-276 |
| 038 | 14 | PA | | | 5-0 | 24-53-21 | TB5022 | 10 | E | * | C01251 | 2 | D | * | 050-099 |
| 038 | 14 | PA | | | 5-0 | 24-53-21 | TB5022 | 10 | E | * | C01251 | 2 | D | * | 150-199, 275-299 |
| 039 | 14 | PA | | | 5-0 | 24-53-21 | C01238 | 2 | D | * | C01180 | 2 | D | | 050-099, 162-199 |
| 039 | 14 | PA | | | 5-0 | 24-53-21 | C01251 | 2 | D | * | C01180 | 2 | D | | 150-157, 275-299 |
| 040 | 14 | PA | | | 3-0 | 24-53-21 | C01416 | 2 | D | * | C01081 | 1 | D | * | 050-099 |
| 040 | 14 | PA | | | 2-0 | 24-53-21 | C01416 | 2 | D | * | C01081 | 1 | D | * | 150-199, 275-299 |
| 041 | 14 | PA | | | 3-0 | 24-53-21 | C01081 | 1 | D | * | C01499 | 1 | D | * | ALL |
| 042 | 10 | PA | | | 2-0 | 24-53-21 | C04100 | 2 | D | * | C01009 | 2 | D | | 050-099 |
| 042 | 14 | PA | | | 2-0 | 24-53-21 | C04100 | 2 | D | * | C01009 | 2 | D | | 150-199, 275-299 |
| 043 | 18 | PA | | | 3-0 | 24-51-24 | C01526 | 1 | D | | C01038 | 1 | D | * | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 31

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|-----------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0038 | 286T0038 | | | P11-R1-BUS DISTRIBUTION (continued) | | | | | | | | | | | | |
| 045 | 08 | PA | | 4-0 | 24-54-21 | TB5022 | 8 | E | | C00703 | 1 | LA | * | ALL | | |
| 046 | 08 | PA | | 2-0 | 24-54-21 | C00703 | 1 | LA | * | C04025 | 1 | LA | * | 050-099, 157, 167-199, 277-299 | | |
| 046 | 08 | PA | | 2-0 | 24-54-21 | C00703 | 1 | LA | * | C04025 | 1 | LA | * | 150-156, 162-166 | | |
| 046 | 08 | PA | | 2-0 | 24-54-21 | C00703 | 1 | / | * | C04037 | 1 | / | * | 275-276 | | |
| 047 | 08 | PA | | 2-0 | 24-54-21 | C04037 | 1 | LA | * | C01202 | 1 | LA | * | 050-099, 157, 167-199, 275-299 | | |
| 047 | 08 | PA | | 2-0 | 24-54-21 | C04037 | 1 | LA | | C01202 | 1 | LA | * | 150-156, 162-166 | | |
| 048 | 08 | PA | | 2-0 | 24-54-21 | C01202 | 1 | LA | * | C01280 | 2 | LA | * | ALL | | |
| 049 | 08 | PA | | 1-0 | 24-54-21 | C01280 | 2 | LA | * | C01223 | 2 | LA | * | 050-099, 150-199 | | |
| 049 | 08 | PA | | 1-0 | 24-54-21 | C01280 | 2 | LA | * | C01194 | 2 | LA | * | 275-299 | | |
| 050 | 08 | PA | | 3-0 | 24-54-21 | C01223 | 2 | LA | * | C00706 | 2 | LA | * | 050-099 | | |
| 050 | 08 | PA | | 3-0 | 24-54-21 | C01223 | 2 | LA | * | C00687 | 2 | LA | * | 150-199 | | |
| 050 | 08 | PA | | 2-0 | 24-54-21 | C01194 | 2 | LA | * | C00687 | 2 | LA | * | 275-299 | | |
| 051 | 08 | PA | | 1-0 | 24-54-21 | C01457 | 2 | D | | C01450 | 1 | LA | * | 050-099 | | |
| 051 | 08 | PA | | 5-0 | 24-54-21 | C01457 | 2 | D | | C01495 | 1 | LA | * | 150-199 | | |
| 052 | 08 | PA | | 2-0 | 24-54-21 | C00706 | 2 | LA | * | C00690 | 1 | LA | * | 050-099 | | |
| 052 | 08 | PA | | 2-0 | 24-54-21 | C00706 | 2 | LA | * | C00697 | 1 | LA | * | 150-199, 275-299 | | |
| 053 | 08 | PA | | 2-0 | 24-54-21 | C00690 | 1 | LA | * | C00661 | 1 | LA | * | 050-099 | | |
| 053 | 08 | PA | | 2-0 | 24-54-21 | C00697 | 1 | LA | * | C00661 | 1 | LA | * | 150-199, 275-299 | | |
| 054 | 08 | PA | | 2-0 | 24-54-21 | C00661 | 1 | LA | * | C01372 | 1 | LA | * | 050-099 | | |
| 054 | 08 | PA | | 3-0 | 24-54-21 | C00661 | 1 | LA | * | C01372 | 1 | LA | * | 150-199, 275-299 | | |
| 056 | 08 | PA | | 5-0 | 24-54-21 | TB5022 | 8 | E | | C00645 | 1 | LA | * | ALL | | |
| 057 | 08 | PA | | 3-0 | 24-54-21 | C00645 | 1 | LA | * | C01461 | 2 | LA | * | 050-099 | | |
| 057 | 08 | PA | | 4-0 | 24-54-21 | C00645 | 1 | LA | * | C01450 | 1 | LA | * | 150, 152-154 | | |
| 057 | 08 | PA | | 4-0 | 24-54-21 | C01450 | 1 | LA | * | C01461 | 2 | LA | * | 151 | | |
| 057 | 08 | PA | | 4-0 | 24-54-21 | C01461 | 2 | LA | * | C01450 | 1 | LA | * | 155-199, 275-276 | | |
| 057 | 08 | PA | | 4-0 | 24-54-21 | C00645 | 1 | LA | * | C01461 | 2 | LA | * | 277-299 | | |
| 058 | 08 | PA | | 2-0 | 24-54-21 | C01450 | 1 | LA | * | C01495 | 1 | LA | * | 150-199 | | |
| 058 | 08 | PA | | 2-0 | 24-54-21 | C01457 | 2 | D | | C01450 | 1 | LA | * | 275-276 | | |
| 058 | 08 | PA | | 2-0 | 24-54-21 | C01457 | 2 | LA | * | C01450 | 1 | D | | 277-299 | | |
| 059 | 08 | PA | | 6-0 | 24-54-21 | TB5022 | 9 | E | | C01561 | 2 | LA | * | ALL | | |
| 060 | 08 | PA | | 2-0 | 24-54-21 | C01561 | 2 | LA | * | C00517 | 1 | LA | * | ALL | | |
| 061 | 08 | PA | | 3-0 | 24-54-21 | C00517 | 1 | LA | * | C00523 | 1 | LA | * | ALL | | |
| 062 | 08 | PA | | 3-0 | 24-54-21 | C00523 | 1 | LA | * | C00623 | 2 | D | | ALL | | |
| 063 | 08 | PA | | 4-0 | 24-54-21 | TB5022 | 9 | E | | C01053 | 2 | LA | * | ALL | | |
| 064 | 08 | PA | | 3-0 | 24-54-21 | C01053 | 2 | LA | * | C01050 | 2 | LA | * | ALL | | |
| 065 | 08 | PA | | 2-0 | 24-54-21 | C01050 | 2 | LA | * | C00838 | 2 | LA | * | ALL | | |
| 066 | 08 | PA | | 2-0 | 24-54-21 | C00838 | 2 | LA | * | C01481 | 1 | LA | * | ALL | | |

WIRE LIST
D280T132

91-21-11
Section W0030
Page 32
May 20/2005



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|----------|-------|---------|-------|------|------|--------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0038 | 286T0038 | | | P11-R1-BUS DISTRIBUTION (continued) | | | | | | | | | | | |
| 067 | 08 | PA | | 2-0 | 24-54-21 | | C01481 | 1 | LA | * | C01096 | 1 | LA | * | ALL |
| 068 | 08 | PA | | 1-0 | 24-54-21 | | C00768 | 2 | LA | * | C00574 | 1 | LA | * | ALL |
| 069 | 08 | PA | | 1-0 | 24-54-21 | | C00574 | 1 | LA | * | C04189 | 1 | LA | * | ALL |
| 070 | 08 | PA | | 2-0 | 24-54-21 | | C04189 | 1 | LA | * | C01548 | 1 | LA | * | ALL |
| 071 | 08 | PA | | 3-0 | 24-54-21 | | C01548 | 1 | LA | * | C01018 | 2 | LA | * | ALL |
| 072 | 08 | PA | | 3-0 | 24-54-21 | | C01018 | 2 | LA | * | C01028 | 2 | LA | * | ALL |
| 073 | 08 | PA | | 3-0 | 24-54-21 | | C01028 | 2 | LA | * | C00560 | 2 | LA | * | ALL |
| 074 | 08 | PA | | 3-0 | 24-54-21 | | C00560 | 2 | LA | * | C00568 | 2 | LA | * | ALL |
| 075 | 08 | PA | | 3-0 | 24-54-21 | | C00568 | 2 | LA | * | C00545 | 1 | LA | * | ALL |
| 076 | 08 | PA | | 2-0 | 24-54-21 | | C00545 | 1 | LA | * | C01532 | 1 | D | | ALL |
| 077 | 08 | PA | | 6-0 | 24-54-21 | | TB5022 | 9 | E | | C01333 | 2 | LA | * | ALL |
| 078 | 08 | PA | | 2-0 | 24-54-21 | | C01333 | 2 | LA | * | C01335 | 2 | LA | * | ALL |
| 079 | 08 | PA | | 1-0 | 24-54-21 | | C01335 | 2 | LA | * | C01340 | 2 | LA | * | 050-099 |
| 079 | 08 | PA | | 2-0 | 24-54-21 | | C01335 | 2 | LA | * | C01344 | 2 | LA | * | 150-199, 275-299 |
| 080 | 08 | PA | | 3-7 | 24-54-21 | | C01340 | 2 | LA | * | C01174 | 2 | LA | * | 050-099 |
| 080 | 08 | PA | | 3-6 | 24-54-21 | | C01344 | 2 | LA | * | C01148 | 1 | LA | * | 150-199, 275-299 |
| 081 | 08 | PA | | 1-0 | 24-54-21 | | C01174 | 2 | LA | * | C01173 | 2 | LA | * | 050-099 |
| 081 | 08 | PA | | 1-0 | 24-54-21 | | C01148 | 1 | LA | * | C01174 | 2 | LA | * | 150-199, 275-299 |
| 082 | 08 | PA | | 1-0 | 24-54-21 | | C00823 | 1 | LA | * | C00740 | 2 | LA | * | 050-099 |
| 082 | 08 | PA | | 2-0 | 24-54-21 | | C00823 | 1 | LA | * | C00795 | 2 | LA | * | 150-199, 275-299 |
| 083 | 08 | PA | | 1-0 | 24-54-21 | | C01130 | 2 | LA | * | C00732 | 2 | LA | * | ALL |
| 084 | 08 | PA | | 2-0 | 24-54-21 | | C01172 | 2 | LA | * | C01170 | 2 | LA | * | 050-099 |
| 084 | 08 | PA | | 1-0 | 24-54-21 | | C00732 | 2 | LA | * | C01320 | 2 | LA | * | 150-199, 275-299 |
| 085 | 08 | PA | | 2-0 | 24-54-21 | | C01144 | 1 | LA | * | C01173 | 2 | LA | * | 050-099 |
| 085 | 08 | PA | | 2-0 | 24-54-21 | | C01170 | 2 | LA | * | C01173 | 2 | LA | * | 150-199, 275-299 |
| 086 | 08 | PA | | 2-0 | 24-54-21 | | C00795 | 2 | LA | * | C01178 | 1 | D | | 050-099 |
| 086 | 08 | PA | | 2-0 | 24-54-21 | | C00823 | 1 | LA | * | C01178 | 1 | D | | 150-199, 275-299 |
| 088 | 08 | PA | | 1-0 | 24-54-21 | | C01130 | 2 | LA | * | C00823 | 1 | LA | * | 050-099 |
| 088 | 08 | PA | | 1-0 | 24-54-21 | | C01130 | 2 | LA | * | C00740 | 2 | LA | * | 150-199 |
| 088 | 08 | PA | | 2-0 | 24-54-21 | | C01130 | 2 | LA | * | C00740 | 2 | LA | * | 275-299 |
| 094 | 14 | PA | | 3-0 | 24-53-21 | | C01499 | 1 | D | * | C04100 | 2 | D | * | ALL |
| 095 | 12 | PA | | 5-0 | 24-51-52 | | C00794 | 2 | D | * | TB5022 | 1 | E | * | ALL |
| 099 | 14 | PA | | 5-0 | 24-53-21 | | TB5022 | 10 | E | | C01416 | 2 | D | * | 050-099 |
| 099 | 14 | PA | | 5-0 | 24-53-21 | | C01416 | 2 | D | * | TB5022 | 10 | E | * | 150-199, 275-299 |
| 106 | 08 | PA | | 4-0 | 24-54-21 | | C00768 | 2 | LA | * | C01096 | 1 | LA | * | ALL |
| 109 | 12 | PA | | 1-0 | 24-51-21 | | C01317 | 1 | D | * | C04229 | 2 | D | | ALL |
| 110 | 12 | PA | | 2-0 | 24-51-21 | | C01336 | 2 | D | * | C04227 | 2 | D | | 050-099 |
| 111 | 16 | PA | | 1-0 | 24-51-21 | | C00636 | 2 | D | * | C00617 | 2 | D | | ALL |
| 112 | 20 | PA | | 5-0 | 24-51-42 | | TB5022 | 14 | E | | C04231 | 1 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0030

Page 33

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0038 | 286T0038 | | | P11-R1-BUS DISTRIBUTION (continued) | | | | | | | | | | | | |
| 113 | 20 | PA | | 5-0 | 24-51-42 | TB5022 | 15 | E | | | C04227 | 1 | D | | ALL | |
| 114 | 20 | PA | | 5-0 | 24-51-42 | TB5022 | 16 | E | | | C04229 | 1 | D | | ALL | |
| 115 | 20 | PA | | 8-0 | 24-51-43 | C00587 | 1 | D | * | | TB5020 | 16 | E | | ALL | |
| 116 | 20 | PA | | 1-0 | 24-51-43 | C00587 | 1 | D | * | | C00601 | 2 | D | | ALL | |
| 117 | 20 | PA | | 8-0 | 24-51-43 | C01239 | 2 | D | | | TB5020 | 16 | E | | ALL | |
| 118 | 20 | PA | | 1-0 | 24-51-43 | C00589 | 1 | D | | | C00581 | 1 | D | * | ALL | |
| 121 | 20 | PA | | 3-0 | 24-51-43 | C00581 | 1 | D | * | | TB0292F | C006 | 2 | | ALL | |
| 122 | 20 | PA | | 1-0 | 24-51-43 | C00605 | 1 | D | | | C00626 | 2 | D | | ALL | |
| 124 | 20 | PA | | 1-0 | 24-51-43 | C00638 | 2 | D | | | C00634 | 1 | D | * | ALL | |
| 125 | 20 | PA | | 3-0 | 24-51-43 | C00634 | 1 | D | * | | TB0292F | C005 | 2 | | ALL | |
| 129 | 08 | PA | | 1-0 | 24-54-21 | C00740 | 2 | LA | * | | C00795 | 2 | LA | * | 150-199, 275-278 | |
| 129 | 08 | PA | | 2-0 | 24-54-21 | C00740 | 2 | LA | * | | C00795 | 2 | LA | * | 280-299 | |
| 130 | 08 | PA | | 1-0 | 24-54-21 | C01320 | 2 | LA | * | | C01353 | 2 | LA | * | 150-199, 275-299 | |
| 131 | 08 | PA | | 1-0 | 24-54-21 | C01144 | 1 | LA | * | | C01170 | 2 | LA | * | 050-099 | |
| 132 | 08 | PA | | 1-0 | 24-54-21 | C01172 | 2 | LA | * | | C01353 | 2 | LA | * | 050-099 | |
| 133 | 08 | PA | | 1-0 | 24-54-21 | C01353 | 2 | LA | * | | C01320 | 2 | LA | * | 050-099 | |
| 134 | 08 | PA | | 1-0 | 24-54-21 | C01320 | 2 | LA | * | | C00732 | 2 | LA | * | 050-099 | |
| 135 | 08 | PA | | 1-0 | 24-54-21 | C00740 | 2 | LA | * | | C00795 | 2 | LA | * | 050-099 | |
| 137 | 12 | PA | | 6-0 | 24-51-24 | C00685 | 1 | D | * | | TB5152 | 4 | E | | 050-099 | |
| 137 | 12 | PA | | 6-0 | 24-51-24 | TB5152 | 4 | E | | | C00685 | 1 | D | * | 150-199, 275-299 | |
| 138 | 18 | PA | | 6-0 | 24-51-24 | C01203 | 1 | D | * | | TB5152 | 6 | E | * | 050-099, 152-199, 280-299 | |
| 138 | 18 | PA | | 6-0 | 24-51-24 | C01203 | 1 | D | | | TB5152 | 6 | E | * | 150-151, 275-278 | |
| 139 | 12 | PA | | 6-0 | 24-51-24 | C01331 | 2 | D | | | TB5152 | 5 | E | * | ALL | |
| 141 | 12 | PA | | 6-0 | 24-51-24 | C01036 | 1 | D | | | TB5152 | 5 | E | * | 050-099 | |
| 141 | 12 | PA | | 6-0 | 24-51-24 | TB5152 | 5 | E | * | | C01036 | 1 | D | | 150-199, 275-299 | |
| 142 | 18 | PA | | 6-0 | 24-51-24 | C01038 | 1 | D | * | | TB5152 | 6 | E | * | 050-099 | |
| 142 | 18 | PA | | 6-0 | 24-51-24 | TB5152 | 6 | E | * | | C01038 | 1 | D | * | 150-199, 275-299 | |
| 143 | 12 | PA | | 6-0 | 24-51-24 | C00682 | 1 | D | | | TB5152 | 7 | E | | ALL | |
| 144 | 08 | PA | | 1-0 | 24-54-21 | C01353 | 2 | LA | * | | C01172 | 2 | LA | * | 150-199, 275-299 | |
| 145 | 08 | PA | | 1-0 | 24-54-21 | C01185 | 2 | LA | * | | C01170 | 2 | LA | * | 150-199, 275-299 | |
| 146 | 08 | PA | | 1-0 | 24-54-21 | C01173 | 2 | LA | * | | C01174 | 2 | LA | * | 150-199, 275-299 | |
| 147 | 12 | PA | | 2-0 | 24-51-24 | C00685 | 1 | D | * | | C00701 | 2 | D | | 050-099 | |
| 147 | 12 | PA | | 3-0 | 24-51-24 | C00685 | 1 | D | * | | C00701 | 2 | D | | 150-199, 275-299 | |
| 150 | 08 | PA | | 1-0 | 24-54-21 | C01185 | 2 | LA | * | | C01172 | 2 | LA | * | 150-199, 275-299 | |
| 152 | 08 | PA | | 1-0 | 24-54-21 | C01495 | 1 | D | | | C01467 | 1 | D | | 275-299 | |
| 154 | 12 | PA | | 2-0 | 24-51-21 | C04180 | 1 | D | * | | C04036 | 1 | D | * | 150-199 | |
| 154 | 12 | PA | | 1-0 | 24-51-21 | C04036 | 1 | D | * | | C04180 | 1 | D | * | 275-299 | |
| 155 | 08 | PA | | 1-0 | 24-54-21 | C00687 | 2 | LA | * | | C00706 | 2 | LA | * | 150-199, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W0030
Page 34
May 20/2005



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|--------|--------|-------|------|--------|--------|-------------|---|------------------|
| | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | | |
| W0038 | 286T0038 | | | P11-R1-BUS DISTRIBUTION (continued) | | | | | | | | | | | |
| 156 | 08 | | PA | | 2-0 | 24-54-21 | C04025 | 1 | LA | * | C04037 | 1 | LA | * | 050-099, 277-299 |
| 159 | 14 | | PA | | 3-0 | 24-51-52 | C01101 | 1 | D | * | C00627 | 1 | D | | 050-099 |
| 159 | 12 | | PA | | 9-0 | 24-51-52 | C01225 | 1 | D | * | C00627 | 1 | D | | 275-276 |
| 166 | 12 | | PA | | 2-0 | 24-51-21 | C01240 | 2 | D | * | C04180 | 1 | D | * | 050-099 |
| 167 | 14 | | PA | | 3-0 | 24-53-21 | C01238 | 2 | D | * | C01251 | 2 | D | * | 050-099 |
| 167 | 14 | | PA | | 4-0 | 24-53-21 | C01238 | 2 | D | * | C01251 | 2 | D | * | 162-199 |
| 168 | 08 | | PA | | 4-0 | 24-54-21 | C01450 | 1 | LA | * | C01461 | 2 | LA | * | 050-099 |
| 168 | 08 | | PA | | 6-0 | 24-54-21 | C01461 | 2 | LA | * | C00645 | 1 | LA | * | 150, 152-154 |
| 168 | 08 | | PA | | 6-0 | 24-54-21 | C01461 | 2 | LA | * | C00645 | 1 | LA | * | 151 |
| 168 | 08 | | PA | | 4-0 | 24-54-21 | C01461 | 2 | LA | * | C00645 | 1 | LA | * | 155-199, 275-276 |
| 169 | 08 | | PA | | 4-0 | 24-54-21 | C01461 | 2 | LA | * | C01457 | 2 | LA | * | 277-299 |
| 173 | 12 | | PA | | 4-0 | 24-51-52 | C01101 | 1 | D | | C00627 | 1 | D | | 150-154 |
| 173 | 12 | | PA | | 3-0 | 24-51-52 | C01101 | 1 | D | * | C00627 | 1 | D | | 155-199 |
| 173 | 14 | | PA | | 3-0 | 24-51-52 | C01101 | 1 | D | * | C00627 | 1 | D | | 277-299 |
| 180 | 08 | | PA | | 2-0 | 24-54-21 | C01372 | 1 | LA | * | C01368 | 1 | D | | ALL |
| 181 | 08 | | PA | | 2-0 | 24-54-21 | C04025 | 1 | / | | C04037 | 1 | / | | 150-156, 162-166 |
| 181 | 08 | | PA | | 2-0 | 24-54-21 | C04025 | 1 | LA | * | C04037 | 1 | LA | * | 157, 167-199 |
| 501 | 12 | | PA | | 2-0 | 24-51-24 | C01203 | 1 | D | * | C01319 | 1 | D | | 050-099, 280-299 |
| 501 | 12 | | PA | | 3-0 | 24-51-24 | C01203 | 1 | D | * | C01319 | 1 | D | | 152-199 |
| 501 | 12 | | PA | | 2-0 | 24-51-24 | C01203 | 1 | D | | C01319 | 1 | D | | 275-276 |
| 501 | 18 | | PA | | 2-0 | 24-51-24 | C01203 | 1 | D | | C01319 | 1 | D | | 277-278 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0040 | 286T0040 | | | P11-L2-LOAD DISTRIBUTION | | | | | | | | | | | |
| 001 | 22 | | PA | 6-9 | 34-22-82 | D04165J | | 1 | | | C00586 | 2 | D | | ALL |
| 002 | 24 | | PK | 6-10 | 34-22-16 | D04165J | | 3 | | | C00593 | 2 | D | | ALL |
| 003 | 24 | | PK | 6-8 | 34-22-16 | D04165J | | 4 | | | C00588 | 2 | D | | ALL |
| 004 | 22 | | PA | 7-0 | 34-13-11 | D04165J | | 5 | | | C00580 | 2 | D | | ALL |
| 005 | 22 | | PA | 6-11 | 34-13-11 | D04165J | | 6 | | | C00584 | 2 | D | | ALL |
| 006 | 24 | | PK | 5-2 | 31-25-11 | D04165J | | 7 | | | C00573 | 1 | D | | ALL |
| 007 | 24 | | PK | 6-10 | 34-22-16 | D04165J | | 8 | | | C00633 | 2 | D | | ALL |
| 008 | 20 | | PA | 7-3 | 34-43-12 | D04165J | | 12 | | | C00615 | 1 | D | | ALL |
| 010 | 22 | | PA | 3-11 | 27-41-11 | D04271J | | 3 | | | C01017 | 1 | D | | ALL |
| 011 | 24 | | PK | 4-1 | 29-11-22 | D05000J | | 11 | | | C01087 | 2 | D | | ALL |
| 012 | 20 | | PA | 5-0 | 22-41-12 | D04271J | | 9 | | | C00520 | 1 | D | | ALL |
| 013 | 24 | | PK | 6-0 | 34-22-16 | D04271J | | 11 | | | C00637 | 1 | D | | ALL |
| 014 | 20 | | PA | 4-6 | 22-11-11 | D04271J | | 13 | | | C00513 | 2 | D | | ALL |
| 015 | 20 | | PA | 4-6 | 22-11-12 | D04271J | | 14 | | | C00522 | 2 | D | | ALL |
| 016 | 20 | | PA | 4-7 | 22-11-12 | D04271J | | 15 | | | C00516 | 2 | D | | ALL |
| 017 | 20 | | PA | 5-1 | 22-31-11 | D04271J | | 16 | | | C00501 | 1 | D | | ALL |
| 018 | 20 | | PA | 4-11 | 22-31-12 | D04271J | | 17 | | | C00512 | 1 | D | | ALL |
| 019 | 20 | | PA | 5-0 | 22-31-12 | D04271J | | 18 | | | C00525 | 1 | D | | ALL |
| 020 | 22 | | PA | 4-6 | 27-21-12 | D04271J | | 5 | | | C01031 | 2 | D | | ALL |
| 023 | 22 | | PA | 12-10 | 24-51-71 | D07962P | | 20 | | | C04126 | 2 | D | | ALL |
| 024 | 22 | | PA | 5-0 | 34-31-11 | D04271J | | 23 | | | C00603 | 2 | D | | ALL |
| 025 | 24 | | PK | 4-0 | 27-48-11 | D04271J | | 24 | | | C01002 | 1 | D | | ALL |
| 026 | 24 | | PK | 5-5 | 34-22-36 | D04271J | | 27 | | | C00639 | 1 | D | | ALL |
| 027 | 22 | | PA | 6-3 | 34-46-11 | D04271J | | 29 | | | C00592 | 1 | D | | ALL |
| 028 | 24 | | PK | 6-6 | 34-21-11 | D04271J | | 31 | | | C00611 | 1 | D | | ALL |
| 029 | 22 | | PA | 4-6 | 27-09-11 | D04273J | | 1 | | | C01531 | 2 | D | | ALL |
| 030 | 22 | | PA | 4-7 | 27-09-11 | D04273J | | 2 | | | C01536 | 2 | D | | ALL |
| 031 | 22 | | PA | 6-3 | 34-61-11 | D04273J | | 5 | | | C00609 | 2 | D | | ALL |
| 032 | 24 | | PK | 6-3 | 34-61-11 | D04273J | | 6 | | | C00597 | 2 | D | | ALL |
| 034 | 20 | | PA | 6-8 | 34-53-11 | D04273J | | 9 | | | C00616 | 1 | D | | 050-099, 155-199, 275-299 |
| 034 | 22 | | PA | 6-8 | 34-53-11 | D04273J | | 9 | | | C00616 | 1 | D | | 150-154 |
| 035 | 24 | | PK | 12-4 | 78-36-11 | D07968P | | 26 | | | C01480 | 1 | D | | ALL |
| 036 | 22 | | PA | 4-9 | 31-31-11 | D04273J | | 13 | | | C00578 | 2 | D | | ALL |
| 037 | 22 | | PA | 4-10 | 31-31-11 | D04273J | | 14 | | | C00561 | 2 | D | | ALL |
| 038 | 24 | | PK | 5-3 | 21-65-11 | D05000J | | 8 | | | C04019 | 2 | D | | ALL |
| 039 | 22 | | PA | 6-2 | 23-21-11 | D04273J | | 17 | | | C00539 | 2 | D | | ALL |
| 041 | 22 | | PA | 5-5 | 23-22-11 | C00559 | | 2 | D | | D04273J | 19 | | | ALL |
| 042 | 22 | | PA | 6-4 | 23-34-11 | D04273J | | 20 | | | C00547 | 2 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 1

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0040 | 286T0040 | | | P11-L2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 043 | 20 | | PA | | 5-4 | 23-11-11 | D04273J | | 25 | | | | C00340 | A2 | D | | ALL |
| 044 | 20 | | PA | | 5-3 | 23-11-11 | D04273J | | 26 | | | | C00340 | B2 | D | | ALL |
| 045 | 20 | | PA | | 5-3 | 23-11-11 | D04273J | | 27 | | | | C00340 | C2 | D | | ALL |
| 046 | 22 | | PA | | 6-10 | 34-33-11 | D04273J | | 29 | | | | C00600 | 1 | D | | ALL |
| 047 | 22 | | PA | | 6-9 | 34-57-11 | D04273J | | 31 | | | | C00607 | 1 | D | | ALL |
| 048 | 16 | | PA | | 11-9 | 33-42-11 | D07970P | | 7 | FM | | | C01247 | 2 | D | | ALL |
| 049 | 16 | | PA | | 11-8 | 33-42-11 | D07970P | | 8 | FM | | | C01248 | 2 | D | | ALL |
| 050 | 18 | | PA | | 6-5 | 33-42-11 | D05000J | | 25 | DK | | | C01249 | 2 | D | | 050-099 |
| 050 | 16 | | PA | | 6-5 | 33-42-11 | D05000J | | 25 | FM | | | C01249 | 2 | D | | 150-199, 275-299 |
| 051 | 20 | | PA | | 6-3 | 33-44-21 | D05000J | | 20 | | | | C01226 | 2 | D | | ALL |
| 052 | 18 | | PA | | 11-5 | 32-35-11 | D07966P | | 19 | DK | | | C01177 | 1 | D | | ALL |
| 053 | 22 | | PA | | 6-8 | 33-13-16 | D05000J | | 9 | | | | C01241 | 1 | D | | ALL |
| 054 | 20 | | PA | | 6-4 | 33-42-21 | D05000J | | 27 | | | | C01276 | 2 | D | | 050-099 |
| 054 | 18 | | PA | | 6-4 | 33-42-21 | D05000J | | 27 | DK | | | C01276 | 2 | D | | 150-199, 275-299 |
| 055 | 20 | | PQ | B | 9-9 | 27-13-11 | D07970P | | 10 | | | | C01016 | 1 | D | | ALL |
| 055Z | | | | B | 0-0 | 27-13-11 | D07970P | | DED | | | | C01016 | DED | | | ALL |
| 056 | 20 | | PQ | C | 9-9 | 27-23-11 | D07970P | | 11 | | | | C01013 | 1 | D | | 050-099 |
| 056 | 18 | | PQ | C | 9-9 | 27-23-11 | D07970P | | 11 | DK | | | C01013 | 1 | D | | 150-199, 275-299 |
| 056Z | | | | C | 0-0 | 27-23-11 | D07970P | | DED | | | | C01013 | DED | | | ALL |
| 057 | 22 | | PA | | 5-3 | 74-31-11 | D05000J | | 16 | | | | SP01484 | | 9 | | ALL |
| 058 | 22 | | PA | | 6-0 | 30-43-11 | D05000J | | 33 | | | | C01136 | CAP | Y | | 050-099, 150-199 |
| 058 | 22 | | PA | | 6-0 | 30-43-11 | D05000J | | 33 | | | | C01136 | 2 | D | | 275-299 |
| 059 | 24 | | PK | | 11-2 | 32-42-11 | D07966P | | 22 | | | | C01171 | 1 | D | | ALL |
| 060 | 24 | | PK | | 11-7 | 32-42-11 | D07966P | | 21 | | | | C01176 | 1 | D | | ALL |
| 063 | 22 | | PQ | D | 4-1 | 29-11-31 | D05000J | | 12 | | | | C01085 | 2 | D | | ALL |
| 063Z | | | | D | 0-0 | 29-11-31 | D05000J | | DED | | | | C01085 | DED | | | ALL |
| 064 | 16 | | PA | | 6-1 | 23-12-31 | C00556 | | 2 | D | | | D04273J | 21 | | | 050-099 |
| 064 | 16 | | PA | | 6-1 | 23-12-31 | D04273J | | 21 | | | | C00556 | 2 | D | | 150-199, 275-299 |
| 065 | 24 | | PK | | 5-0 | 30-21-11 | D05000J | | 31 | | | | C01147 | 2 | D | | 050-099 |
| 065 | 24 | | PK | | 6-2 | 30-21-11 | D05000J | | 31 | | | | C01147 | 2 | D | | 150-199, 275-299 |
| 066 | 20 | | PA | | 12-9 | 24-51-13 | D07962P | | 19 | | | | C00822 | 2 | D | | ALL |
| 067 | 24 | | PK | | 10-8 | 27-18-11 | D07964P | | 22 | | | | C04099 | 1 | D | | ALL |
| 068 | 20 | | PA | | 13-2 | 27-21-11 | D07964P | | 8 | | | | C01033 | 2 | D | | ALL |
| 069 | 24 | | PK | | 10-7 | 27-28-11 | D07964P | | 9 | | | | C01005 | 1 | D | | ALL |
| 070 | 24 | | PK | | 10-6 | 27-28-13 | D07964P | | 10 | | | | C01034 | 1 | D | | ALL |
| 071 | 24 | | PK | | 10-9 | 27-51-31 | D07964P | | 12 | | | | C01019 | 2 | D | | ALL |
| 073 | 24 | | PK | | 11-1 | 27-51-61 | D07964P | | 15 | | | | C01521 | 2 | D | | ALL |
| 074 | 24 | | PK | | 11-2 | 27-51-61 | D07964P | | 14 | | | | C01524 | 2 | D | | ALL |
| 076 | 24 | | PK | | 10-10 | 27-51-51 | D07964P | | 13 | | | | C01022 | 2 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 2

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0040 | 286T0040 | | | P11-L2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 077 | 24 | | PK | 12-9 | 21-61-51 | D07960P | | 25 | | | | | C00670 | 2 | D | | ALL |
| 078 | 24 | | PK | 10-7 | 27-58-11 | D07964P | | 17 | | | | | C01522 | 2 | D | | ALL |
| 079 | 24 | | PK | 10-8 | 27-58-11 | D07964P | | 16 | | | | | C01008 | 2 | D | | ALL |
| 081 | 22 | | PA | 4-11 | 31-31-15 | D04273J | | 32 | | | | | C00672 | 2 | D | | ALL |
| 082 | 24 | | PK | 10-6 | 27-58-21 | D07964P | | 19 | | | | | C01523 | 2 | D | | ALL |
| 083 | 24 | | PK | 13-3 | 27-58-11 | D07964P | | 18 | | | | | C01021 | 2 | D | | ALL |
| 084 | 24 | | PK | 10-9 | 27-81-31 | D07964P | | 21 | | | | | C01020 | 1 | D | | ALL |
| 085 | 24 | | PK | 6-9 | 33-42-11 | D05000J | | 26 | | | | | C01259 | 2 | D | | ALL |
| 086 | 24 | | PK | 10-8 | 27-11-11 | D07964P | | 6 | | | | | C01035 | 1 | D | | ALL |
| 087 | 24 | | PK | 11-10 | 24-11-11 | D07962P | | 16 | | | | | C00837 | 1 | D | | ALL |
| 088 | 16 | | PA | 6-2 | 25-31-21 | D05000J | | 30 | FM | | | | C00737 | 1 | D | | 050-099, 150-199, 275-276 |
| 088 | 16 | | PA | 6-2 | 25-31-21 | D05000J | | 30 | FM | | | | C00742 | 1 | D | | 277-299 |
| 089 | 20 | | PA | 11-6 | 27-62-11 | D07964P | | 20 | | | | | C01023 | 2 | D | | ALL |
| 090 | 20 | | PA | 10-2 | 27-13-11 | D07968P | | 10 | | | | | C01014 | 1 | D | | ALL |
| 091 | 20 | | PA | 10-0 | 27-23-11 | D07968P | | 11 | | | | | C01011 | 1 | D | | 050-099 |
| 091 | 18 | | PA | 10-0 | 27-23-11 | D07968P | | 11 | DK | | | | C01011 | 1 | D | | 150-199, 275-299 |
| 093 | 24 | | PK | 12-9 | 30-31-11 | D07962P | | 27 | | | | | C01120 | 2 | D | | ALL |
| 095 | 24 | | PK | 11-2 | 77-31-11 | D07968P | | 23 | | | | | C01464 | 1 | D | | ALL |
| 096 | 24 | | PK | 12-3 | 78-34-11 | D07968P | | 24 | | | | | C01482 | 1 | D | | ALL |
| 098 | 24 | | PK | 11-0 | 73-33-11 | C01415 | | 1 | D | | | | D07968P | 29 | | | ALL |
| 100 | 22 | | PA | 10-7 | 79-32-11 | D07968P | | 27 | | | | | C01498 | 2 | D | | ALL |
| 101 | 16 | | PA | 11-0 | 73-21-20 | D07968P | | 18 | FM | | | | C01465 | 2 | D | | 050-099, 275-299 |
| 101 | 20 | | PA | 11-0 | 73-21-20 | D07968P | | 18 | | | | | C01465 | 2 | D | | 150-199 |
| 102 | 22 | | PA | 6-1 | 34-55-11 | D04273J | | 10 | | | | | C00582 | 2 | D | | ALL |
| 103 | 20 | | PA | 11-1 | 73-21-19 | D07968P | | 21 | | | | | C01458 | 1 | D | | ALL |
| 104 | 24 | | PK | 12-1 | 73-21-17 | D07968P | | 16 | | | | | C01404 | 1 | D | | ALL |
| 105 | 24 | | PK | 10-11 | 28-43-11 | D07966P | | 13 | | | | | C01412 | 1 | D | | ALL |
| 106 | 22 | | PQ | 12-0 | 33-16-12 | D07970P | | 2 | | | | | C01297 | 2 | D | | ALL |
| 106Z | | | | 0-0 | 33-16-12 | D07970P | | DED | | | | | C01297 | DED | | | ALL |
| 107 | 24 | | PK | 11-7 | 21-25-11 | D07960P | | 1 | | | | | C00660 | 2 | D | | ALL |
| 109 | 20 | | PA | 5-4 | 21-31-11 | D05000J | | 1 | | | | | C00686 | 1 | D | | ALL |
| 110 | 22 | | PA | 12-4 | 33-16-12 | D07968P | | 2 | | | | | C01293 | 2 | D | * | ALL |
| 111 | 22 | | PQ | 12-2 | 33-16-12 | D07968P | | 3 | | | | | C01298 | 2 | D | | ALL |
| 111Z | | | | 0-0 | 33-16-12 | D07968P | | DED | | | | | C01298 | DED | | | ALL |
| 112 | 24 | | PK | 11-8 | 21-58-13 | D07960P | | 15 | | | | | C00651 | 1 | D | | ALL |
| 113 | 22 | | PA | 12-5 | 21-51-11 | D07960P | | 3 | | | | | C00653 | 2 | D | | ALL |
| 114 | 22 | | PA | 12-4 | 33-16-17 | D07968P | | 4 | | | | | C01293 | 2 | D | * | ALL |
| 115 | 24 | | PK | 11-8 | 21-53-11 | D07960P | | 8 | | | | | C00673 | 2 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 3

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0040 | 286T0040 | | | P11-L2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 116 | 24 | | PK | | 11-7 | 21-53-11 | D07960P | | 7 | | | | C00702 | 2 | D | | ALL |
| 117 | 24 | | PK | | 11-9 | 21-58-14 | D07960P | | 14 | | | | C00654 | 1 | D | | ALL |
| 120 | 24 | | PK | | 11-2 | 21-52-41 | D07960P | | 6 | | | | C00709 | 2 | D | | ALL |
| 124 | 24 | | PK | | 12-4 | 78-36-11 | D07968P | | 25 | | | | C01480 | 1 | D | | ALL |
| 125 | 20 | | PA | | 11-4 | 33-42-21 | D07970P | | 13 | | | | C01312 | 2 | D | | 050-099 |
| 125 | 18 | | PA | | 11-4 | 33-42-21 | C01312 | | 2 | D | | | D07970P | 13 | DK | | 150-199, 275-299 |
| 126 | 24 | | PK | | 10-7 | 75-23-11 | D07968P | | 17 | | | | C01449 | 1 | D | | ALL |
| 131 | 24 | | PK | | 4-5 | 28-22-12 | D05000J | | 38 | | | | C01049 | 1 | D | | ALL |
| 132 | 24 | | PK | | 10-4 | 29-31-11 | D07966P | | 10 | | | | C01080 | 2 | D | | ALL |
| 133 | 24 | | PK | | 11-4 | 21-51-23 | D07960P | | 5 | | | | C04038 | 2 | D | | ALL |
| 134 | 24 | | PK | | 11-3 | 21-51-23 | D07960P | | 4 | | | | C04039 | 2 | D | | ALL |
| 135 | 24 | | PK | | 11-11 | 30-41-11 | D07962P | | 28 | | | | C01128 | 2 | D | | ALL |
| 136 | 24 | | PK | | 11-4 | 32-09-11 | D07966P | | 18 | | | | C01182 | 1 | D | | ALL |
| 137 | 22 | | PA | | 10-11 | 31-41-11 | D07970P | | 5 | | | | C04078 | 2 | D | | ALL |
| 138 | 24 | | PK | | 12-0 | 33-11-11 | D07968P | | 1 | | | | C01289 | 1 | D | | ALL |
| 140 | 24 | | PK | | 12-3 | 33-13-11 | D07968P | | 15 | | | | C01237 | 1 | D | * | ALL |
| 142 | 22 | | PA | | 12-1 | 33-13-18 | D07970P | | 15 | | | | C01242 | 1 | D | | ALL |
| 143 | 24 | | PK | | 4-4 | 28-22-11 | D05000J | | 37 | | | | C01054 | 1 | D | | ALL |
| 144 | 24 | | PK | | 11-10 | 33-14-21 | D07968P | | 14 | | | | C01252 | 1 | D | | ALL |
| 145 | 22 | | PA | | 11-0 | 23-51-41 | D07966P | | 5 | | | | SP01568 | 9 | | | ALL |
| 146 | 24 | | PK | | 11-9 | 33-16-11 | D07970P | | 9 | | | | C01309 | 2 | D | | ALL |
| 150 | 18 | | PA | | 12-5 | 38-32-11 | D07962P | | 12 | DK | | | C01367 | 2 | D | | ALL |
| 151 | 24 | | PK | | 11-6 | 36-21-11 | D07962P | | 7 | | | | C04221 | 1 | D | | ALL |
| 153 | 22 | | PA | | 11-9 | 33-26-11 | D07968P | | 8 | | | | C01316 | 2 | D | | ALL |
| 157 | 16 | | PA | | 11-11 | 33-26-21 | D07968P | | 9 | FM | | | C01318 | 2 | D | | ALL |
| 160 | 24 | | PK | | 11-3 | 21-53-22 | D07960P | | 9 | | | | C04039 | 2 | D | | ALL |
| 161 | 24 | | PK | | 11-4 | 21-53-22 | D07960P | | 10 | | | | C04038 | 2 | D | | ALL |
| 163 | 24 | | PK | | 11-10 | 21-26-11 | D07960P | | 2 | | | | C00705 | 1 | D | | ALL |
| 165 | 24 | | PK | | 11-6 | 21-61-51 | D07960P | | 26 | | | | C00667 | 2 | D | | ALL |
| 166 | 24 | | PK | | 12-9 | 36-11-11 | D07962P | | 2 | | | | C01334 | 2 | D | | ALL |
| 167 | 24 | | PK | | 11-10 | 36-11-11 | D07962P | | 1 | | | | C01330 | 1 | D | | ALL |
| 168 | 24 | | PK | | 11-7 | 36-11-31 | D07962P | | 4 | | | | C01338 | 1 | D | | ALL |
| 169 | 24 | | PK | | 11-8 | 36-11-31 | D07962P | | 3 | | | | C01337 | 1 | D | | ALL |
| 175 | 22 | | PQ | E | 4-5 | 29-21-32 | D04165J | | 9 | | | | C01085 | 2 | D | | ALL |
| 175Z | | | | E | 0-0 | 29-21-32 | D04165J | | DED | | | | C01085 | DED | | | ALL |
| 178 | 24 | | PK | | 10-7 | 29-31-11 | D07962P | | 10 | | | | C01082 | 2 | D | | ALL |
| 179 | 24 | | PK | | 11-6 | 36-21-11 | D07962P | | 8 | | | | C01332 | 1 | D | | ALL |
| 182 | 24 | | PK | | 10-9 | 27-38-11 | D07964P | | 11 | | | | C04101 | 1 | D | | ALL |
| 184 | 22 | | PA | | 7-0 | 74-31-11 | D02158 | | A1 | | | | C01430 | 1 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 4

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|---|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0040 | 286T0040 | | | P11-L2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 185 | 22 | | PA | 8-4 | 74-31-11 | D02158 | A3 | | | | | | C01434 | 1 | D | | ALL |
| 186 | 22 | | PA | 2-1 | 74-31-11 | D02158 | B2 | | | | | | D02158 | A2 | | | ALL |
| 187 | 22 | | PA | 6-3 | 74-31-11 | D02158 | B3 | | | | | | SP01484 | | 9 | | ALL |
| 188 | 22 | | PA | 5-4 | 31-41-11 | D04165J | 2 | | | | | | C04081 | 2 | D | | ALL |
| 191 | 24 | | PK | 6-5 | 74-31-11 | D02158 | X1 | | | | | | C01439 | 1 | D | | ALL |
| 192 | 20 | | PA | 2-0 | 74-31-11 | D02158 | X2 | | | | | | GD0001 | A.. | 2 | | ALL |
| 193 | 24 | | PK | 1-10 | 24-51-31 | TB0292F | A001 | 2 | | | | | R00001 | = A | \$ | | ALL |
| 195 | 18 | | PA | 5-5 | 30-42-11 | D05000J | 21 | | | | | | C01143 | 2 | D | * | ALL |
| 196 | 24 | | PK | 11-4 | 32-46-11 | C01181 | 1 | D | | | | | D07966P | 23 | | | 050-099 |
| 196 | 24 | | PK | 11-4 | 32-46-11 | D07966P | 23 | | | | | | C01181 | 1 | D | | 150-199, 275-299 |
| 197 | 24 | | PK | 7-1 | 24-51-31 | C00824 | 2 | D | | | | | TB0292F | A001 | 2 | | ALL |
| 198 | 22 | | PA | 10-6 | 29-11-11 | D07966P | 1 | | | | | | C01095 | 2 | D | | ALL |
| 199 | 22 | | PA | 12-7 | 52-11-12 | D07962P | 24 | | | | | | C01402 | 2 | D | | 050-099, 150-199 |
| 199 | 20 | | PA | 12-7 | 52-11-12 | D07962P | 24 | | | | | | C01402 | 2 | D | | 275-299 |
| 20A | 22 | | PA | 5-4 | 31-36-11 | C00571 | 2 | D | | | | | D04273J | 18 | | | ALL |
| 20B | 22 | | PA | 11-3 | 32-45-11 | C01186 | 1 | D | | | | | D07966P | 2 | | | 050-099, 150-156, 163-199, 275-299 |
| 20B | 22 | | PA | 11-3 | 32-45-11 | C01186 | CAP | Y | | | | | D07966P | 2 | | | 157-162 |
| 357B | 24 | | PM | A | 5-3 | 33-13-19 | D05000J | 10 | | | | | SP02364 | | 9 | | ALL |
| 357R | 24 | | PM | A | 0-0 | 33-13-19 | D05000J | 22 | | | | | SP02362 | | 9 | | ALL |
| 357Y | 24 | | PM | A | 0-0 | 33-13-19 | D05000J | 24 | | | | | SP02366 | | 9 | | ALL |
| 504 | 22 | | PA | 5-1 | 31-35-11 | C00569 | 2 | D | | | | | D04273J | 37 | | | 050-099, 275-299 |
| 504 | 22 | | PA | 5-1 | 31-35-11 | D04273J | 37 | | | | | | C00569 | 2 | D | | 150-199 |
| 508 | 24 | | PK | 6-4 | 34-53-13 | C04423 | 1 | D | | | | | D04273J | 39 | | | 050-099, 150-154, 156-157, 166-199, 277-299 |
| 508 | 24 | | PK | 6-4 | 34-53-13 | C04423 | 1 | D | | | | | D04273J | 23 | | | 155, 162-165, 275-276 |
| 511 | 24 | | PK | 11-0 | 21-61-71 | C04027 | 1 | D | | | | | D07960P | 19 | | | ALL |
| 512 | 24 | | PK | 11-3 | 21-61-71 | C04182 | 1 | D | | | | | D07960P | 20 | | | ALL |
| 513 | 24 | | PK | 11-9 | 21-61-51 | C00668 | 2 | D | | | | | D07960P | 13 | | | ALL |
| 514 | 24 | | PK | 11-1 | 21-61-61 | C04026 | 1 | D | | | | | D07960P | 16 | | | 150-199 |
| 515 | 24 | | PK | 11-4 | 21-61-61 | C04181 | 1 | D | | | | | D07960P | 18 | | | 150-199 |
| 516 | 20 | | PA | 4-6 | 28-31-11 | C01065 | 1 | D | | | | | D05000J | 13 | | | 050-099, 155-199, 276-299 |
| 517 | 20 | | PA | 10-8 | 28-31-12 | C01067 | 1 | D | | | | | D07960P | 21 | | | 050-099, 155-199, 276-299 |
| 519 | 16 | | PA | 11-0 | 73-21-11 | C01460 | 2 | D | | | | | D07966P | 4 | FM | | ALL |
| 522 | 16 | | PA | 4-9 | 23-25-11 | C00506 | 1 | D | | | | | D04273J | 36 | FM | | 150, 153-155, 162-165 |

WIRE LIST
D280T132

91-21-11
Section W0040
Page 5
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|---|---|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0040 | 286T0040 | | | P11-L2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | | | |
| 522 | 16 | | PA | | 4-9 | 23-25-11 | C00506 | | 1 | D | | | | D04273J | 23 | | | | 156-157, 166-199, 277-299 |
| 524 | 24 | | PK | | 4-10 | 23-25-14 | C00724 | | 1 | D | | | | D04273J | 24 | | | | 150, 153-199, 277-299 |
| 605 | 24 | | PK | | 11-1 | 21-61-61 | C04026 | | 1 | D | | | | D07960P | 16 | | | | 050-099, 275-299 |
| 606 | 24 | | PK | | 11-4 | 21-61-61 | C04181 | | 1 | D | | | | D07960P | 18 | | | | 050-099, 275-299 |
| 702 | 24 | | PK | | 12-0 | 36-11-51 | D07962P | | 6 | | | | | C01343 | 1 | D | | | ALL |
| 704 | 20 | | PA | | 5-2 | 34-22-16 | D04271J | | 12 | | | | | C00622 | 2 | D | | | ALL |
| 705 | 24 | | PK | | 6-6 | 52-51-11 | D05000J | | 18 | | | | | C01400 | 2 | D | | | ALL |
| 706 | 24 | | PK | | 11-6 | 33-24-11 | D07970P | | 6 | | | | | C01254 | 1 | D | | | ALL |
| 709 | 22 | | PA | | 6-3 | 74-31-11 | D02158 | | | B1 | | | | SP01484 | | | 9 | | ALL |
| 70B | 24 | | PK | | 11-8 | 21-45-22 | C00692 | | 2 | D | | | | D07960P | 17 | | | | ALL |
| 70E | 20 | | PA | | 4-6 | 29-11-14 | C01090 | | 2 | D | | | | D05000J | 35 | | | | ALL |
| 710 | 20 | | PA | | 1-7 | 74-31-11 | D00716 | | | D3 | | | | GD0001 | D.. | 2 | | | ALL |
| 711 | 22 | | PQ | K | 5-3 | 74-31-21 | D00716 | | | B3 | | | | SP01470 | | | 9 | | ALL |
| 711Z | | | | K | 0-0 | 74-31-21 | D00716 | | | DED | | | | SP01470 | DED | | | | ALL |
| 712 | 22 | | PQ | L | 5-3 | 74-31-21 | D00716 | | | B1 | | | | SP01470 | | | 9 | | ALL |
| 712Z | | | | L | 0-0 | 74-31-21 | D00716 | | | DED | | | | SP01470 | DED | | | | ALL |
| 713 | 22 | | PA | | 7-11 | 74-31-11 | D00716 | | | A3 | | | | C01434 | 1 | D | | | ALL |
| 714 | 22 | | PQ | M | 6-6 | 74-31-21 | D00716 | | | A1 | | | | C01432 | 1 | D | | | ALL |
| 714Z | | | | M | 0-0 | 74-31-21 | D00716 | | | DED | | | | C01432 | DED | | | | ALL |
| 715 | 24 | | PK | | 5-5 | 74-31-11 | D00716 | | | X1 | | | | C01439 | 1 | D | | | ALL |
| 716 | 20 | | PA | | 1-7 | 74-31-11 | D00716 | | | X2 | | | | GD0001 | A.. | 2 | | | ALL |
| 717 | 24 | | PK | | 6-2 | 74-31-11 | D00716 | | | D2 | | | | D05000J | 15 | | | | ALL |
| 718 | 22 | | PQ | N | 0-7 | 74-31-21 | D00716 | | | B2 | | | | D00716 | A2 | | | | ALL |
| 718Z | | | | N | 0-0 | 74-31-21 | D00716 | | | DED | | | | D00716 | DED | | | | ALL |
| 719 | 18 | | PA | | 11-11 | 36-11-51 | D07962P | | 5 | DK | | | | C01339 | 1 | D | | | ALL |
| 721 | 24 | | PK | | 11-4 | 21-24-11 | C00677 | | 2 | D | | | | D07960P | 27 | | | | 050-099, 150-199 |
| 722 | 20 | | PA | | 11-3 | 33-42-21 | D07970P | | 12 | | | | | C01313 | 2 | D | | | 050-099 |
| 722 | 18 | | PA | | 11-3 | 33-42-21 | C01313 | | 2 | D | | | | D07970P | 12 | DK | | | 150-199, 275-299 |
| 727 | 24 | | PK | | 12-3 | 33-11-13 | D07968P | | 13 | | | | | C01237 | 1 | D | | * | ALL |
| 728 | 24 | | PK | | 6-9 | 33-13-16 | D05000J | | 29 | | | | | C01237 | 1 | D | | * | ALL |
| 729 | 16 | | PA | | 4-6 | 27-32-31 | D05000J | | 6 | FM | | | | C01024 | 1 | D | | | ALL |
| 732 | 16 | | PA | | 5-5 | 30-42-11 | D05000J | | 23 | | | | | C01143 | 2 | D | | * | ALL |
| 741 | 16 | | PA | | 6-1 | 25-31-31 | C00741 | | 1 | D | | | | D05000J | 5 | FM | | | 277-299 |
| 748 | 22 | | PA | | 6-10 | 33-13-19 | C01244 | | 1 | D | | | | SP02360 | 9 | | | | ALL |
| 750 | 24 | | PK | | 11-7 | 33-11-13 | D07970P | | 16 | | | | | C04280 | 1 | D | | | ALL |
| 760 | 24 | | PK | | 11-8 | 21-45-21 | C00692 | | 2 | D | | | | D07960P | 28 | | | | ALL |
| 761 | 24 | | PK | | 6-2 | 33-13-16 | C01232 | | 1 | D | | | | D05000J | 17 | | | | ALL |
| 762 | 22 | | PA | | 12-9 | 24-25-11 | C00847 | | 2 | D | | | | D07962P | 18 | | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0040 | 286T0040 | | | P11-L2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | |
| 775 | 16 | | PA | | 11-0 | 73-21-20 | D07968P | 6 | FM | | C01466 | 2 | D | | 050-099 |
| 775 | 16 | | PA | | 11-0 | 73-21-20 | C01466 | 2 | D | | D07968P | 6 | FM | | 150-199, 275-299 |
| 780 | 18 | | PA | | 12-7 | 38-32-14 | C01371 | 2 | D | | D07962P | 9 | GB | | 050-099 |
| 780 | 18 | | PA | | 12-7 | 38-32-14 | C01371 | 2 | D | | D07962P | 9 | DK | | 150-199, 275-299 |
| 790 | 20 | | PA | | 5-2 | 34-45-11 | C00628 | 1 | D | | D04271J | 33 | | | 050-099, 153-199, 277-299 |
| 790 | 20 | | PA | | 5-2 | 34-45-11 | C00628 | 1 | D | | D04271J | 10 | | | 150-152 |
| 825 | 20 | | PA | | 11-7 | 30-81-11 | C01118 | 2 | D | | D07960P | 22 | | | 050-099, 150-199 |
| 905 | 20 | | PA | | 4-9 | 23-25-13 | C00901 | 1 | D | | D04273J | 22 | | | 150, 153-199 |
| 908 | 16 | | PA | | 4-9 | 23-25-11 | C00902 | 1 | D | | D04273J | 12 | FM | | 156-157, 166-199 |
| 910 | 16 | | PA | | 4-9 | 23-25-11 | C00506 | 1 | D | | D04273J | 12 | FM | | 150, 153-155, 162-165 |
| 911 | 22 | | PA | | 7-0 | 34-46-13 | C09007 | 1 | D | | D04271J | 28 | | | 150, 152-199, 275-299 |
| W0041 | 286T0041 | | | MID CABIN PARTITION ATTENDANT HANDSET | | | | | | | | | | | |
| 401B | 24 | | PY | QA | 10-0 | 23-42-11 | D00851 | 3 | \$D | | D04669P | 3 | | | 050-099, 275-299 |
| 401B | 24 | | PY | QA | 11-0 | 23-42-11 | D00851 | 3 | \$D | | D04669P | 3 | | | 150-199 |
| 401G | 24 | | PY | QA | 0-0 | 23-42-11 | D00851 | 5 | \$D | | D04669P | 5 | | | ALL |
| 401R | 24 | | PY | QA | 0-0 | 23-42-11 | D00851 | 1 | \$D | | D04669P | 1 | | | ALL |
| 401Y | 24 | | PY | QA | 0-0 | 23-42-11 | D00851 | 4 | \$D | | D04669P | 4 | | | ALL |
| 401Z | | | | QA | 0-0 | 23-42-11 | D00851 | 2 | \$D | | D04669P | 2 | | | ALL |
| W0042 | 286T0042 | | | P11-R2-LOAD DISTRIBUTION | | | | | | | | | | | |
| 001 | 24 | | PK | | 10-5 | 24-51-52 | D07974P | 20 | | | C00853 | 2 | D | | ALL |
| 002 | 24 | | PK | | 10-1 | 27-58-21 | D07976P | 19 | | | C01526 | 2 | D | | ALL |
| 003 | 18 | | PA | | 9-11 | 27-51-11 | D07976P | 8 | DK | | C01027 | 2 | D | | ALL |
| 004 | 18 | | PA | | 9-10 | 27-81-11 | D07976P | 6 | DK | | C01028 | 1 | D | | ALL |
| 005 | 18 | | PA | | 9-11 | 27-81-21 | D07976P | 7 | DK | | C01029 | 1 | D | | ALL |
| 006 | 24 | | PK | | 10-3 | 27-51-61 | D07976P | 15 | | | C01038 | 2 | D | | ALL |
| 007 | 24 | | PK | | 10-4 | 27-51-61 | D07976P | 14 | | | C01036 | 2 | D | | ALL |
| 008 | 22 | | PA | | 9-11 | 33-13-13 | D07986P | 15 | | | C01239 | 1 | D | * | ALL |
| 009 | 24 | | PK | | 9-10 | 33-13-17 | D07988P | 15 | | | C01240 | 1 | D | | ALL |
| 010 | 22 | | PA | | 6-3 | 33-11-16 | D05006J | 19 | | | C01251 | 1 | D | | ALL |
| 013 | 24 | | PK | | 9-6 | 36-11-21 | D07974P | 1 | | | C01331 | 1 | D | | ALL |
| 014 | 22 | | PA | | 10-7 | 33-25-11 | D07978P | 6 | | | C01223 | 1 | D | | 050-099, 150-199 |
| 014 | 22 | | PA | | 10-7 | 33-25-11 | D07978P | 6 | | | C01194 | 1 | D | | 275-299 |
| 015 | 20 | | PA | | 5-2 | 21-31-21 | D05006J | 1 | | | C00701 | 1 | D | | ALL |
| 016 | 22 | | PA | | 11-4 | 79-32-11 | D07986P | 27 | | | C01499 | 2 | D | | ALL |
| 018 | 24 | | PK | | 10-3 | 27-18-11 | D07976P | 22 | | | C04100 | 1 | D | | ALL |
| 019 | 24 | | PK | | 10-2 | 27-38-11 | D07976P | 23 | | | C04102 | 1 | D | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0040
Page 7
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|---|---|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0042 | 286T0042 | | | P11-R2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | | |
| 01A | 22 | | PA | | 9-8 | 21-26-31 | C00693 | | 1 | D | | | | D07972P | 26 | | | ALL |
| 01B | 24 | | PK | | 9-6 | 21-61-81 | C04025 | | 2 | D | | | | D07972P | 6 | | | ALL |
| 01C | 24 | | PK | | 9-6 | 21-61-81 | C04180 | | 2 | D | | | | D07972P | 14 | | | ALL |
| 01D | 24 | | PK | | 7-7 | 34-61-26 | C00726 | | 2 | D | | | | D04187J | 2 | | | 050-099 |
| 01D | 24 | | PK | | 7-7 | 34-61-26 | C00726 | | 1 | D | | | | D04187J | 2 | | | 150-199, 275-299 |
| 020 | 16 | | PA | | 10-11 | 73-21-20 | D07986P | | 18 | FM | | | | C01467 | 2 | D | | 050-099, 275-299 |
| 020 | 20 | | PA | | 10-11 | 73-21-20 | D07986P | | 18 | | | | | C01467 | 2 | D | | 150-199 |
| 021 | 18 | | PA | | 4-3 | 78-34-21 | D10958 | | A1 | | | | | C01483 | 2 | D | | 050-099 |
| 021 | 18 | | PA | | 4-3 | 78-34-21 | C01483 | | 2 | D | | | | D10958 | A1 | | | 150-199, 275-299 |
| 022 | 24 | | PK | | 4-9 | 73-21-17 | D10878 | | B1 | | | | | C01405 | 1 | D | | ALL |
| 023 | 22 | | PA | | 9-11 | 33-16-12 | D07986P | | 2 | | | | | C01273 | 2 | D | | ALL |
| 024 | 22 | | PQ | G | 10-1 | 33-16-12 | D07986P | | 3 | | | | | C01284 | 2 | D | * | ALL |
| 024Z | | | | G | 0-0 | 33-16-12 | D07986P | | DED | | | | | C01284 | DED | | | ALL |
| 025 | 22 | | PQ | K | 6-8 | 74-31-21 | D02156 | | A1 | | | | | C01433 | 1 | D | | ALL |
| 025Z | | | | K | 0-0 | 74-31-21 | D02156 | | DED | | | | | C01433 | DED | | | ALL |
| 026 | 22 | | PA | | 10-1 | 33-16-17 | D07986P | | 4 | | | | | C01284 | 2 | D | * | ALL |
| 027 | 24 | | PK | | 12-3 | 30-31-21 | D07974P | | 27 | | | | | C01121 | 2 | D | | ALL |
| 028 | 24 | | PK | | 10-5 | 29-33-11 | D07978P | | 2 | | | | | C01101 | 2 | D | | ALL |
| 029 | 24 | | PK | | 4-5 | 32-09-12 | D10878 | | D1 | | | | | C01170 | 1 | D | | 050-099 |
| 029 | 24 | | PK | | 4-4 | 32-09-12 | D10878 | | D1 | | | | | C01170 | 1 | D | | 150-199, 275-299 |
| 030 | 24 | | PK | | 12-3 | 21-51-21 | D07972P | | 3 | | | | | C00704 | 2 | D | | ALL |
| 031 | 24 | | PK | | 9-8 | 32-42-12 | D07978P | | 22 | | | | | C01173 | 1 | D | | ALL |
| 032 | 24 | | PK | | 10-4 | 29-31-11 | D07988P | | 10 | | | | | C01081 | 2 | D | | ALL |
| 033 | 24 | | PK | | 9-9 | 21-53-12 | D07972P | | 9 | | | | | C04037 | 2 | D | | ALL |
| 034 | 24 | | PK | | 9-8 | 21-53-12 | D07972P | | 10 | | | | | C04036 | 2 | D | | ALL |
| 035 | 24 | | PK | | 4-10 | 29-11-12 | D05006J | | 11 | | | | | C01084 | 2 | D | | ALL |
| 036 | 22 | | PA | | 10-7 | 29-11-21 | D07978P | | 1 | | | | | C01096 | 2 | D | | ALL |
| 037 | 24 | | PK | | 9-4 | 21-53-21 | D07972P | | 8 | | | | | C00674 | 2 | D | | ALL |
| 038 | 24 | | PK | | 9-5 | 21-53-21 | D07972P | | 7 | | | | | C00703 | 2 | D | | ALL |
| 039 | 22 | | PQ | F | 4-11 | 74-31-11 | D02156 | | A3 | | | | | SP01472 | | | 9 | ALL |
| 039Z | | | | F | 0-0 | 74-31-11 | D02156 | | DED | | | | | SP01472 | DED | | | ALL |
| 040 | 24 | | PK | | 9-11 | 21-25-21 | D07972P | | 1 | | | | | C00661 | 2 | D | | ALL |
| 042 | 24 | | PK | | 9-10 | 21-58-15 | D07972P | | 16 | | | | | C00687 | 1 | D | | ALL |
| 043 | 24 | | PK | | 9-7 | 21-26-11 | D07972P | | 2 | | | | | C00706 | 1 | D | | ALL |
| 044 | 22 | | PQ | H | 9-9 | 33-16-12 | D07988P | | 2 | | | | | C01274 | 2 | D | | ALL |
| 044Z | | | | H | 0-0 | 33-16-12 | D07988P | | DED | | | | | C01274 | DED | | | ALL |
| 045 | 18 | | PA | | 10-6 | 33-51-11 | D07986P | | 6 | DK | | | | C01280 | 1 | D | | ALL |
| 046 | 20 | | PA | | 10-3 | 33-21-21 | D07986P | | 22 | | | | | C01203 | 2 | D | | ALL |
| 047 | 18 | | PA | | 10-5 | 33-51-11 | D07986P | | 7 | DK | | | | C01302 | 1 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 8

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0042 | 286T0042 | | | P11-R2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | |
| 048 | 20 | PA | | | 11-6 | 73-21-19 | D07986P | | 21 | | C01457 | 1 | D | | ALL |
| 049 | 22 | PA | | | 10-6 | 33-26-11 | D07986P | | 8 | | C01317 | 2 | D | | ALL |
| 050 | 22 | PQ | M | | 0-7 | 74-31-21 | D02156 | | B2 | | D02156 | A2 | | | ALL |
| 050Z | | | M | | 0-0 | 74-31-21 | D02156 | DED | | | D02156 | DED | | | ALL |
| 051 | 22 | PQ | N | | 4-11 | 74-31-21 | D02156 | | B3 | | SP01468 | | 9 | | ALL |
| 051Z | | | N | | 0-0 | 74-31-21 | D02156 | DED | | | SP01468 | DED | | | ALL |
| 052 | 24 | PK | | | 10-0 | 21-61-11 | D07972P | | 19 | | C04029 | 2 | D | | ALL |
| 053 | 24 | PK | | | 10-0 | 21-61-11 | D07972P | | 20 | | C04184 | 1 | D | | ALL |
| 054 | 24 | PK | | | 10-1 | 21-61-21 | D07972P | | 21 | | C04030 | 2 | D | | ALL |
| 055 | 24 | PK | | | 10-0 | 21-61-21 | D07972P | | 22 | | C04185 | 1 | D | | ALL |
| 056 | 24 | PK | | | 10-2 | 21-61-31 | D07972P | | 23 | | C04031 | 2 | D | | ALL |
| 057 | 24 | PK | | | 10-2 | 21-61-31 | D07972P | | 24 | | C04186 | 1 | D | | ALL |
| 058 | 24 | PK | | | 11-0 | 32-09-21 | D07978P | | 19 | | C01178 | 2 | D | | ALL |
| 059 | 24 | PK | | | 4-6 | 78-34-21 | D10876 | A1 | | | C01483 | 2 | D | | ALL |
| 060 | 24 | PK | | | 5-0 | 21-43-11 | D05006J | | 3 | | C00685 | 2 | D | | ALL |
| 061 | 24 | PK | | | 4-11 | 21-43-11 | D05006J | | 2 | | C00697 | 2 | D | | ALL |
| 062 | 24 | PK | | | 5-1 | 21-44-11 | D05006J | | 5 | | C00691 | 2 | D | | ALL |
| 063 | 22 | PA | | | 10-3 | 25-29-11 | D07974P | | 21 | | C00732 | 1 | D | | ALL |
| 064 | 24 | PK | | | 9-9 | 21-58-14 | D07972P | | 15 | | C00656 | 1 | D | | ALL |
| 069 | 16 | PA | | | 5-1 | 23-12-21 | D04187J | | 56 | | C00545 | 2 | D | | ALL |
| 070 | 22 | PA | | | 3-11 | 27-41-21 | D04187J | | 3 | | C01018 | 1 | D | | ALL |
| 071 | 22 | PA | | | 4-9 | 27-09-11 | D04187J | | 5 | | C01535 | 2 | D | | ALL |
| 072 | 22 | PA | | | 4-10 | 27-09-11 | D04187J | | 7 | | C01532 | 2 | D | | ALL |
| 073 | 22 | PA | | | 7-2 | 34-31-21 | D04187J | | 11 | | C00605 | 2 | D | | ALL |
| 074 | 20 | PA | | | 7-5 | 22-11-21 | D04187J | | 13 | | C00514 | 2 | D | | ALL |
| 075 | 22 | PA | | | 7-4 | 22-11-22 | D04187J | | 14 | | C00517 | 2 | D | | ALL |
| 076 | 22 | PA | | | 7-6 | 22-11-22 | D04187J | | 15 | | C00523 | 2 | D | | ALL |
| 077 | 22 | PA | | | 7-3 | 34-51-21 | D04187J | | 16 | | C00596 | 2 | D | | ALL |
| 078 | 20 | PA | | | 7-2 | 34-53-21 | D04187J | | 17 | | C00617 | 1 | D | | 050-099, 155-199, 275-299 |
| 078 | 22 | PA | | | 7-2 | 34-53-21 | D04187J | | 17 | | C00617 | 1 | D | | 150-154 |
| 079 | 22 | PA | | | 7-3 | 34-55-21 | D04187J | | 18 | | C00583 | 2 | D | | ALL |
| 080 | 22 | PA | | | 7-4 | 34-12-21 | D04187J | | 19 | | C00626 | 1 | D | | ALL |
| 081 | 22 | PA | | | 7-5 | 34-12-21 | D04187J | | 20 | | C00003 | 1 | D | | ALL |
| 082 | 22 | PA | | | 7-6 | 34-12-21 | D04187J | | 21 | | C00004 | 1 | D | | ALL |
| 083 | 22 | PA | | | 7-7 | 34-12-21 | D04187J | | 22 | | C00003 | 2 | D | | ALL |
| 084 | 24 | PK | | | 7-3 | 34-22-26 | D04187J | | 23 | | C00638 | 1 | D | | ALL |
| 085 | 24 | PK | | | 3-10 | 27-48-11 | D04187J | | 24 | | C01009 | 1 | D | | ALL |
| 086 | 22 | PA | | | 7-1 | 34-61-21 | D04187J | | 25 | | C00610 | 2 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0042 | 286T0042 | | | P11-R2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 087 | 24 | | PK | 7-0 | 34-61-21 | D04187J | 26 | | | | | | C00598 | 2 | D | | ALL |
| 089 | 20 | | PA | 6-6 | 23-32-11 | C00540 | 2 | D | | | | | D04187J | 29 | | | 050-099 |
| 089 | 20 | | PA | 6-6 | 23-32-11 | D04187J | 29 | | | | | | C00540 | 2 | D | | 150-199, 275-299 |
| 090 | 24 | | PK | 6-9 | 34-21-21 | D04187J | 31 | | | | | | C00612 | 1 | D | | ALL |
| 091 | 22 | | PA | 4-11 | 23-71-11 | D04187J | 32 | | | | | | C00532 | 1 | D | | ALL |
| 092 | 22 | | PQ | 4-2 | 74-31-21 | D05006J | 16 | | | | | | SP01470 | 9 | | | ALL |
| 092Z | | | P | 0-0 | 74-31-21 | D05006J | DED | | | | | | SP01470 | DED | | | ALL |
| 093 | 22 | | PA | 5-2 | 31-41-11 | D04193J | 4 | | | | | | C04082 | 2 | D | | ALL |
| 094 | 22 | | PA | 5-4 | 31-41-11 | D04193J | 22 | | | | | | C04094 | 2 | D | | ALL |
| 095 | 20 | | PA | 2-3 | 74-31-11 | D02156 | X2 | | | | | | GD0001 | A.. | 2 | | ALL |
| 097 | 20 | | PQ | 6-1 | 22-11-32 | D05187J | 1 | | | | | | C00524 | 2 | D | | ALL |
| 097Z | | | A | 0-0 | 22-11-32 | D05187J | DED | | | | | | C00524 | DED | | | ALL |
| 099 | 20 | | PQ | 6-0 | 22-11-31 | D05187J | 3 | | | | | | C00515 | 2 | D | | ALL |
| 099Z | | | C | 0-0 | 22-11-31 | D05187J | DED | | | | | | C00515 | DED | | | ALL |
| 100 | 20 | | PA | 10-7 | 24-51-23 | D07974P | 19 | | | | | | C00823 | 2 | D | | ALL |
| 101 | 20 | | PA | 10-1 | 27-13-11 | D07976P | 10 | | | | | | C01015 | 1 | D | | ALL |
| 102 | 20 | | PA | 10-2 | 27-23-11 | D07976P | 11 | | | | | | C01012 | 1 | D | | ALL |
| 103 | 20 | | PA | 6-5 | 25-31-11 | D05006J | 30 | | | | | | C00740 | 1 | D | | 050-099 |
| 103 | 20 | | PA | 6-5 | 25-31-11 | D05006J | 30 | DK | | | | | C00740 | 1 | D | | 150-199 |
| 103 | 16 | | PA | 6-5 | 25-31-11 | D05006J | 30 | FM | | | | | C00740 | 1 | D | | 275-299 |
| 108 | 18 | | PA | 10-8 | 38-32-11 | D07974P | 12 | DK | | | | | C01368 | 2 | D | | ALL |
| 109 | 22 | | PA | 10-4 | 31-41-17 | D07988P | 5 | | | | | | C04189 | 2 | D | | ALL |
| 110 | 18 | | PA | 5-0 | 78-34-21 | D10958 | A3 | | | | | | C01479 | 1 | D | | 050-099 |
| 110 | 18 | | PA | 5-0 | 78-34-21 | C01479 | 1 | D | | | | | D10958 | A3 | | | 150-199, 275-299 |
| 112 | 24 | | PK | 4-4 | 78-36-21 | D10878 | A1 | | | | | | C01481 | 2 | D | | ALL |
| 113 | 24 | | PK | 11-3 | 75-23-11 | D07986P | 17 | | | | | | C01450 | 2 | D | | ALL |
| 114 | 24 | | PK | 10-1 | 78-36-21 | D07986P | 25 | | | | | | D10878 | A2 | | | ALL |
| 115 | 24 | | PK | 5-2 | 28-22-12 | D05006J | 38 | | | | | | C01050 | 1 | D | | ALL |
| 116 | 24 | | PK | 4-3 | 36-11-21 | D10876 | C1 | | | | | | C01335 | 1 | D | | ALL |
| 117 | 18 | | PA | 10-3 | 28-41-12 | D07988P | 11 | DK | | | | | C01053 | 1 | D | | ALL |
| 120 | 24 | | PK | 9-8 | 36-11-41 | D07974P | 4 | | | | | | C01333 | 1 | D | | ALL |
| 121 | 24 | | PK | 5-3 | 28-22-11 | D05006J | 37 | | | | | | C01055 | 1 | D | | ALL |
| 122 | 24 | | PK | 7-6 | 34-22-91 | D04193J | 8 | | | | | | C00636 | 1 | D | | ALL |
| 123 | 22 | | PA | 7-4 | 34-22-92 | D04193J | 9 | | | | | | C00587 | 2 | D | | ALL |
| 124 | 24 | | PK | 7-5 | 34-22-26 | D04193J | 10 | | | | | | C00589 | 2 | D | | ALL |
| 125 | 24 | | PK | 7-2 | 34-22-26 | D04193J | 11 | | | | | | C00594 | 2 | D | | ALL |
| 126 | 24 | | PK | 7-3 | 34-22-26 | D04193J | 12 | | | | | | C00634 | 2 | D | | ALL |
| 127 | 22 | | PA | 7-0 | 34-13-21 | D04193J | 13 | | | | | | C00581 | 2 | D | | ALL |
| 128 | 22 | | PA | 7-1 | 34-13-21 | D04193J | 14 | | | | | | C00585 | 2 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 10

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|---------------|---------|-------|------|------|--------|-------|------|--------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0042 | 286T0042 | | | P11-R2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 129 | 24 | | PK | | 6-1 31-25-11 | D04193J | | 16 | | | | | C00574 | 2 | D | | ALL |
| 131 | 22 | | PA | | 7-7 34-33-21 | D04193J | | 18 | | | | | C00601 | 1 | D | | ALL |
| 132 | 24 | | PK | | 4-11 31-51-11 | D04187J | | 30 | | | | | C00565 | 2 | D | | ALL |
| 133 | 24 | | PK | | 9-8 21-51-13 | D07972P | | 5 | | | | | C04036 | 2 | D | | ALL |
| 134 | 24 | | PK | | 9-9 21-51-13 | D07972P | | 4 | | | | | C04037 | 2 | D | | ALL |
| 135 | 20 | | PA | | 7-4 34-43-22 | D04193J | | 28 | | | | | C00599 | 1 | D | | ALL |
| 136 | 22 | | PA | | 12-5 30-11-11 | D07974P | | 26 | | | | | C01132 | 2 | D | | ALL |
| 137 | 22 | | PA | | 10-3 31-41-11 | D07988P | | 4 | | | | | C04079 | 2 | D | | ALL |
| 138 | 18 | | PA | | 6-1 33-42-11 | D05006J | | 26 | DK | | | | C01250 | 2 | D | | 050-099 |
| 138 | 16 | | PA | | 6-1 33-42-11 | D05006J | | 26 | FM | | | | C01250 | 2 | D | | 150-199, 275-299 |
| 139 | 22 | | PA | | 5-4 30-43-11 | D05006J | | 33 | | | | | C01145 | CAP | Y | | 050-099, 150-199 |
| 139 | 22 | | PA | | 5-4 30-43-11 | D05006J | | 33 | | | | | C01145 | 2 | D | | 275-299 |
| 140 | 24 | | PK | | 10-1 32-42-11 | D07978P | | 21 | | | | | C01172 | 1 | D | | ALL |
| 141 | 20 | | PA | | 6-2 33-44-11 | D05006J | | 20 | | | | | C01225 | 2 | D | | ALL |
| 145 | 20 | | PA | | 6-3 33-41-11 | D05006J | | 28 | | | | | C01227 | 2 | D | | 050-099 |
| 145 | 18 | | PA | | 6-3 33-41-11 | D05006J | | 28 | DK | | | | C01227 | 2 | D | | 150-199, 275-299 |
| 146 | 24 | | PK | | 4-5 30-21-11 | D10876 | | B1 | | | | | C01148 | 2 | D | | ALL |
| 147 | 20 | | PA | | 6-1 33-43-11 | D05006J | | 9 | | | | | C01193 | 1 | D | | 050-099 |
| 147 | 18 | | PA | | 6-1 33-43-11 | D05006J | | 9 | DK | | | | C01193 | 1 | D | | 150-199, 275-299 |
| 149 | 20 | | PA | | 6-0 33-42-11 | D05006J | | 25 | | | | | C01202 | 2 | D | | ALL |
| 150 | 20 | | PA | | 7-11 22-21-21 | D05006J | | 36 | | | | | C01561 | 1 | D | | ALL |
| 152 | 20 | | PA | | 5-5 33-43-11 | D05006J | | 24 | | | | | C01192 | 1 | D | | 050-099 |
| 152 | 18 | | PA | | 5-5 33-43-11 | D05006J | | 24 | DK | | | | C01192 | 1 | D | | 150-199, 275-299 |
| 154 | 18 | | PA | | 5-4 30-42-11 | D05006J | | 21 | | | | | C01144 | 2 | D | * | ALL |
| 155 | 22 | | PA | | 5-0 23-43-11 | D05006J | | 39 | | | | | C00560 | 1 | D | | ALL |
| 156 | 24 | | PV | D | 6-4 34-21-31 | D05187J | | 6 | | | | | C00613 | 1 | D | | ALL |
| 156Z | | | | D | 0-0 34-21-31 | D05187J | | DED | | | | | C00613 | DED | | | ALL |
| 157 | 20 | | PQ | E | 6-3 34-33-31 | D05187J | | 9 | | | | | C00602 | 1 | D | | ALL |
| 157Z | | | | E | 0-0 34-33-31 | D05187J | | DED | | | | | C00602 | DED | | | ALL |
| 158 | 20 | | PA | | 9-7 36-11-41 | D07974P | | 3 | | | | | C01336 | 1 | D | | ALL |
| 159 | 24 | | PK | | 5-0 21-44-11 | D05006J | | 4 | | | | | C00690 | 2 | D | | ALL |
| 160 | 22 | | PA | | 9-7 32-31-11 | D07978P | | 20 | | | | | C01174 | 1 | D | | ALL |
| 161 | 16 | | PA | | 10-5 33-26-21 | D07986P | | 9 | FM | | | | C01319 | 2 | D | | ALL |
| 162 | 24 | | PV | J | 4-9 29-11-31 | D05006J | | 12 | | | | | C01086 | 2 | D | | ALL |
| 162Z | | | | J | 0-0 29-11-31 | D05006J | | DED | | | | | C01086 | DED | | | ALL |
| 164 | 24 | | PK | | 9-9 36-21-11 | D07974P | | 7 | | | | | C01342 | 1 | D | | ALL |
| 165 | 24 | | PK | | 10-2 38-15-11 | D07974P | | 11 | | | | | C01353 | 1 | D | | ALL |
| 166 | 24 | | PK | | 10-9 52-71-11 | D07974P | | 23 | | | | | C01406 | 2 | D | | ALL |
| 168 | 24 | | PK | | 1-10 24-51-31 | TB0292F | | A002 | 2 | | | | R00002 | = A | \$ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0042 | 286T0042 | | | P11-R2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 169 | 22 | PA | | 6-11 | 34-22-26 | D04187J | | 9 | | | | | C00623 | 1 | D | | ALL |
| 170 | 24 | PK | | 11-7 | 24-11-21 | D07974P | | 16 | | | | | C00838 | 1 | D | | ALL |
| 171 | 20 | PA | | 4-0 | 27-32-21 | D04187J | | 12 | | | | | C01548 | 2 | D | | ALL |
| 172 | 20 | PA | | 6-5 | 23-11-21 | D04193J | | 1 | | | | | C00341 | A2 | D | | ALL |
| 173 | 20 | PA | | 6-5 | 23-11-21 | D04193J | | 2 | | | | | C00341 | B2 | D | | ALL |
| 174 | 20 | PA | | 6-6 | 23-11-21 | D04193J | | 3 | | | | | C00341 | C2 | D | | ALL |
| 175 | 24 | PK | | 10-0 | 33-14-31 | D07988P | | 14 | | | | | C01281 | 1 | D | | ALL |
| 176 | 24 | PK | | 10-2 | 33-14-11 | D07986P | | 14 | | | | | C01251 | 1 | D | | ALL |
| 177 | 24 | PK | | 9-9 | 21-58-11 | D07972P | | 11 | | | | | C00656 | 1 | D | | ALL |
| 178 | 18 | PA | | 9-5 | 36-11-52 | D07974P | | 5 | DK | | | | C01340 | 1 | D | | ALL |
| 179 | 24 | PK | | 9-4 | 36-11-52 | D07974P | | 6 | | | | | C01344 | 1 | D | | ALL |
| 180 | 20 | PA | | 10-4 | 26-16-21 | D07976P | | 17 | | | | | C00795 | 1 | D | | ALL |
| 181 | 24 | PK | | 6-6 | 24-51-31 | C00825 | | 2 | D | | | | TB0292F | A002 | 2 | | ALL |
| 183 | 20 | PA | | 10-8 | 24-41-11 | D07974P | | 18 | | | | | C00803 | 2 | D | | ALL |
| 185 | 24 | PK | | 5-2 | 21-44-21 | D05006J | | 7 | | | | | C00682 | 2 | D | | ALL |
| 186 | 24 | PK | | 5-1 | 21-44-21 | D05006J | | 6 | | | | | C00689 | 2 | D | | ALL |
| 187 | 24 | PK | | 9-9 | 21-58-16 | D07972P | | 17 | | | | | C00656 | 1 | D | | ALL |
| 188 | 20 | PA | | 6-1 | 33-42-21 | D05006J | | 27 | | | | | C01277 | 2 | D | | 050-099 |
| 188 | 18 | PA | | 6-1 | 33-42-21 | D05006J | | 27 | DK | | | | C01277 | 2 | D | | 150-199, 275-299 |
| 190 | 20 | PA | | 10-1 | 33-21-11 | C01216 | | 1 | D | | | | D07988P | 8 | | | 050-099 |
| 191 | 22 | PA | | 5-2 | 23-51-21 | C00647 | | 2 | D | | | | TB0292F | A004 | 2 | | ALL |
| 192 | 22 | PA | | 5-2 | 23-51-11 | C00645 | | 2 | D | | | | TB0292F | A005 | 2 | | ALL |
| 193 | 22 | PA | | 1-10 | 23-51-11 | TB0292F | | A005 | 2 | | | | R00059 | = A | \$ | | ALL |
| 194 | 22 | PA | | 4-5 | 23-51-11 | R00059 | | = C | | | | | SP01568 | | 9 | | ALL |
| 195 | 20 | PA | | 10-4 | 26-16-21 | D07976P | | 1 | | | | | C00794 | 1 | D | | ALL |
| 196 | 22 | PA | | 1-10 | 23-51-21 | TB0292F | | A004 | 2 | | | | R00058 | = A | \$ | | ALL |
| 197 | 22 | PA | | 4-5 | 23-51-21 | R00058 | | = C | | | | | SP01570 | | 9 | | ALL |
| 198 | 24 | PK | | 6-0 | 31-51-12 | D04193J | | 7 | | | | | C00568 | 1 | D | | ALL |
| 20A | 20 | PA | | 10-1 | 33-21-11 | C01216 | | 1 | D | | | | D07988P | 16 | | | 150-199 |
| 20B | 18 | PA | | 11-7 | 26-13-11 | C00770 | | 1 | DK | | | | D07978P | 16 | DK | | 050-099, 150-199 |
| 520 | 22 | PA | | 12-6 | 78-36-11 | C01493 | | 2 | D | | | | D07986P | 5 | | | ALL |
| 521 | 22 | PA | | 4-10 | 78-36-21 | D10958 | | B3 | | | | | C01494 | 2 | D | | 050-099 |
| 521 | 22 | PA | | 4-10 | 78-36-21 | C01494 | | 2 | D | | | | D10958 | B3 | | | 150-199, 275-299 |
| 522 | 22 | PA | | 3-11 | 78-36-21 | D10958 | | B1 | | | | | C01495 | 2 | D | | 050-099 |
| 522 | 22 | PA | | 3-11 | 78-36-21 | C01495 | | 2 | D | | | | D10958 | B1 | | | 150-199, 275-299 |
| 523 | 22 | PA | | 9-10 | 78-36-21 | D10958 | | B2 | | | | | D07986P | 1 | | | 050-099, 150-199 |
| 523 | 22 | PA | | 9-10 | 78-36-21 | D07986P | | 1 | | | | | D10958 | B2 | | | 275-299 |
| 531 | 22 | PA | | 10-7 | 30-46-11 | C01130 | | 1 | D | | | | D07972P | 25 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 12

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|---|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0042 | 286T0042 | | | P11-R2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | | |
| 537 | 20 | | PA | | 5-0 | 28-31-11 | C01066 | | 1 | D | | | | D05006J | 13 | | | 050-099, 155-199, 276-299 |
| 538 | 20 | | PA | | 11-1 | 28-31-12 | C01068 | | 1 | D | | | | D07972P | 27 | | | 050-099, 155-199, 276-299 |
| 539 | 16 | | PA | | 10-7 | 73-21-11 | C01461 | | 1 | D | | | | D07976P | 4 | FM | | ALL |
| 546 | 20 | | PQ | BB | 25-0 | 28-22-31 | C01070 | | 1 | D | | | | D07972P | 29 | | | ALL |
| 546Z | | | | BB | 0-0 | 28-22-31 | C01070 | | | DED | | | | D07972P | DED | | | ALL |
| 547 | 20 | | PQ | BC | 25-0 | 28-22-31 | C01069 | | 1 | D | | | | D07972P | 30 | | | ALL |
| 547Z | | | | BC | 0-0 | 28-22-31 | C01069 | | | DED | | | | D07972P | DED | | | ALL |
| 600 | 22 | | PA | | 10-0 | 33-22-33 | C01238 | | 1 | D | | | | D07986P | 28 | | | 050-099, 162-199 |
| 601 | 22 | | PA | | 4-11 | 34-61-15 | C00627 | | 2 | D | | | | D05006J | 32 | | | ALL |
| 602 | 24 | | PK | | 4-6 | 32-09-12 | C01575 | | 2 | D | | | | D10878 | D3 | | | ALL |
| 603 | 24 | | PK | | 10-3 | 32-09-12 | D07978P | | 18 | | | | | D10878 | D2 | | | ALL |
| 700 | 22 | | PQ | R | 4-11 | 74-31-21 | D02156 | | | B1 | | | | SP01468 | | 9 | | ALL |
| 700Z | | | | R | 0-0 | 74-31-21 | D02156 | | | DED | | | | SP01468 | DED | | | ALL |
| 701 | 20 | | PA | | 2-0 | 74-31-11 | D00800 | | | D3 | | | | GDX0001 | D.. | 2 | | ALL |
| 702 | 22 | | PA | | 4-8 | 74-31-11 | D00800 | | | B3 | | | | SP01474 | | 9 | | ALL |
| 703 | 22 | | PA | | 4-8 | 74-31-11 | D00800 | | | B1 | | | | SP01474 | | 9 | | ALL |
| 704 | 22 | | PA | | 4-8 | 74-31-11 | D00800 | | | A3 | | | | SP01472 | | 9 | | ALL |
| 705 | 22 | | PA | | 6-3 | 74-31-11 | D00800 | | | A1 | | | | C01431 | 1 | D | | ALL |
| 706 | 24 | | PK | | 6-11 | 74-31-11 | D00800 | | | X1 | | | | C01440 | 1 | D | | ALL |
| 707 | 20 | | PA | | 2-0 | 74-31-11 | D00800 | | | X2 | | | | GDX0001 | A.. | 2 | | ALL |
| 708 | 24 | | PK | | 4-8 | 74-31-11 | D00800 | | | D2 | | | | SP01986 | | 9 | | ALL |
| 709 | 22 | | PA | | 2-0 | 74-31-11 | D00800 | | | B2 | | | | D00800 | A2 | | | ALL |
| 710 | 24 | | PK | | 11-7 | 73-33-11 | C01416 | | 1 | D | | | | D07986P | 29 | | | ALL |
| 715 | 18 | | PA | | 10-2 | 32-71-11 | C01185 | | 1 | D | | | | D07972P | 18 | DK | | 150-199, 275-299 |
| 716 | 24 | | PK | | 7-2 | 74-31-11 | D02156 | | | X1 | | | | C01440 | 1 | D | | ALL |
| 720 | 24 | | PK | | 10-3 | 35-11-13 | D07974P | | 38 | | | | | C01320 | 1 | D | | ALL |
| 721 | 22 | | PA | | 9-8 | 33-13-21 | D07988P | | 1 | | | | | C01239 | 1 | D | * | ALL |
| 722 | 20 | | PA | | 10-11 | 24-32-41 | D07974P | | 14 | | | | | C00865 | 2 | D | | 275-299 |
| 723 | 24 | | PK | | 9-9 | 32-41-11 | D07978P | | 23 | | | | | C01180 | 1 | D | | ALL |
| 730R | 22 | | PH | | 4-9 | 26-11-11 | C00763 | | 1 | D | | | | TB0286D | A002 | 2 | | ALL |
| 731R | 22 | | PH | | 1-8 | 26-11-11 | TB0286D | | C002 | 2 | | | | TB0286D | C001 | 2 | | ALL |
| 732R | 22 | | PH | | 5-1 | 26-11-12 | C00767 | | 1 | D | | | | TB0286D | A003 | 2 | | ALL |
| 733R | 22 | | PH | | 1-8 | 26-11-12 | TB0286D | | C003 | 2 | | | | TB0286D | C004 | 2 | | ALL |
| 734R | 22 | | PH | | 4-10 | 26-11-21 | C00764 | | 1 | D | | | | TB0286D | A006 | 2 | | ALL |
| 735R | 22 | | PH | | 1-8 | 26-11-21 | TB0286D | | C005 | 2 | | | | TB0286D | C006 | 2 | | ALL |
| 736R | 22 | | PH | | 5-2 | 26-11-22 | C00768 | | 1 | D | | | | TB0286D | A008 | 2 | | ALL |
| 737R | 22 | | PH | | 1-8 | 26-11-22 | TB0286D | | C007 | 2 | | | | TB0286D | C008 | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0040
Page 13
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0042 | 286T0042 | | | P11-R2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | |
| 738R | 22 | | PH | | 4-11 | 26-15-11 | C00765 | | 1 | D | | TB0286D | A010 | 2 | | ALL |
| 739R | 22 | | PH | | 1-8 | 26-15-11 | TB0286D | | C009 | 2 | | TB0286D | C010 | 2 | | ALL |
| 740R | 24 | | PP | | 5-0 | 26-16-11 | C00766 | | 1 | D | | TB0286D | A012 | 2 | | ALL |
| 741R | 24 | | PP | | 1-8 | 26-16-11 | TB0286D | | C011 | 2 | | TB0286D | C012 | 2 | | ALL |
| 742 | 16 | | PA | | 5-4 | 30-42-11 | D05006J | | 23 | | | C01144 | 2 | D | * | ALL |
| 743 | 24 | | PK | | 10-1 | 21-61-41 | D07972P | | 12 | | | C04028 | 2 | D | | ALL |
| 744 | 24 | | PK | | 10-1 | 21-61-41 | D07972P | | 13 | | | C04183 | 1 | D | | ALL |
| 745 | 24 | | PK | | 4-6 | 36-11-21 | C01345 | | 2 | D | | D10876 | C3 | | | 050-099 |
| 745 | 24 | | PK | | 4-6 | 36-11-21 | D10876 | | C3 | | | C01345 | 2 | D | | 150-199, 275-299 |
| 746 | 24 | | PK | | 10-4 | 36-11-21 | D10876 | | C2 | | | D07974P | 2 | | | ALL |
| 747 | 24 | | PK | | 4-9 | 30-21-11 | C01140 | | 2 | D | | D10876 | B3 | | | 050-099 |
| 747 | 24 | | PK | | 4-9 | 30-21-11 | D10876 | | B3 | | | C01140 | 2 | D | | 150-199, 275-299 |
| 748 | 24 | | PK | | 4-5 | 30-21-11 | D05006J | | 31 | | | D10876 | B2 | | | 050-099 |
| 748 | 24 | | PK | | 4-5 | 30-21-11 | D10876 | | B2 | | | D05006J | 31 | | | 150-199, 275-299 |
| 749 | 24 | | PK | | 4-7 | 73-21-17 | C01401 | | 2 | D | | D10878 | B3 | | | 050-099 |
| 749 | 24 | | PK | | 4-7 | 73-21-17 | D10878 | | B3 | | | C01401 | 2 | D | | 150-199, 275-299 |
| 750 | 24 | | PK | | 10-1 | 73-21-17 | D07986P | | 16 | | | D10878 | B2 | | | 050-099 |
| 750 | 24 | | PK | | 10-1 | 73-21-17 | D10878 | | B2 | | | D07986P | 16 | | | 150-199, 275-299 |
| 751 | 24 | | PK | | 10-2 | 78-34-21 | D07986P | | 24 | | | D10876 | A2 | | | 050-099 |
| 751 | 24 | | PK | | 10-2 | 78-34-21 | D10876 | | A2 | | | D07986P | 24 | | | 150-199, 275-299 |
| 752 | 24 | | PK | | 5-4 | 78-34-21 | D10876 | | A3 | | | C01479 | 1 | D | | ALL |
| 753 | 20 | | PA | | 4-5 | 78-34-21 | D10876 | | X2 | | | D05006J | 14 | | | ALL |
| 754 | 24 | | PK | | 4-8 | 78-34-21 | D10876 | | X1 | | | C01486 | 1 | D | | ALL |
| 755 | 24 | | PK | | 4-7 | 78-34-21 | D10878 | | X1 | | | C01486 | 1 | D | | ALL |
| 756 | 20 | | PA | | 4-4 | 78-34-21 | D10878 | | X2 | | | D05006J | 15 | | | ALL |
| 757 | 24 | | PK | | 5-2 | 78-36-21 | D10878 | | A3 | | | C01478 | 1 | D | | ALL |
| 758 | 22 | | PA | | 10-0 | 24-25-11 | C00848 | | 2 | D | | D07976P | 13 | | | ALL |
| 771 | 18 | | PA | | 9-10 | 78-34-21 | D10958 | | C2 | | | D07986P | 23 | DK | | 050-099, 150-156, 162-199 |
| 771 | 18 | | PA | | 9-10 | SPARE | D10958 | | C2 | | | D07986P | 23 | DK | | 157 |
| 771 | 18 | | PA | | 9-10 | SPARE | D07986P | | 23 | DK | | D10958 | C2 | | | 275-276 |
| 771 | 18 | | PA | | 9-10 | 78-34-21 | D07986P | | 23 | DK | | D10958 | C2 | | | 277-299 |
| 772 | 18 | | PA | | 9-10 | 78-34-21 | D10958 | | A2 | | | D07986P | 12 | DK | | 050-099 |
| 772 | 18 | | PA | | 9-10 | 78-34-21 | D07986P | | 12 | DK | | D10958 | A2 | | | 150-199, 275-299 |
| 777 | 22 | | PA | | 4-5 | 78-34-21 | C01486 | | 1 | D | | D10958 | X1 | | | ALL |
| 778 | 20 | | PA | | 4-2 | 78-34-21 | D10958 | | X2 | | | D05006J | 35 | | | ALL |
| 781 | 16 | | PA | | 11-0 | 73-21-20 | C01468 | | 2 | D | | D07986P | 41 | FM | | ALL |
| 786 | 24 | | PK | | 11-11 | 73-21-11 | C01462 | | 2 | D | | D07986P | 36 | | | ALL |
| 787 | 24 | | PK | | 12-0 | 73-21-11 | C01463 | | 2 | D | | D07986P | 35 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 14

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|----------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0042 | 286T0042 | | | P11-R2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 788 | 18 | | PA | | 10-6 38-32-14 | C01372 | | 2 | D | | | | D07974P | 13 | DK | | ALL |
| 798 | 18 | | PA | | 9-6 36-11-52 | D07974P | | 8 | DK | | | | C01351 | 2 | D | | 150-154 |
| 825 | 20 | | PA | | 10-2 30-81-11 | C01119 | | 2 | D | | | | D07972P | 28 | | | 050-099, 150-199 |
| W0044 | 286T0044 | | | P11-S2-LOAD DISTRIBUTION | | | | | | | | | | | | | |
| 001 | 24 | | PK | | 7-11 28-22-11 | D05012J | | 2 | | | | | C01052 | 1 | D | | ALL |
| 002 | 24 | | PK | | 11-5 32-09-11 | D07984P | | 18 | | | | | C01175 | 2 | D | | ALL |
| 003 | 24 | | PK | | 11-11 33-16-11 | D07980P | | 29 | | | | | C01307 | 2 | D | | ALL |
| 004R | 22 | | PH | | 4-4 26-11-11 | TB0286D | A001 | 2 | | | | | C00774 | 1 | D | | ALL |
| 005 | 22 | | PA | | 1-7 33-51-11 | D05010J | | 6 | | | | | D05708J | 7 | | | 050-099 |
| 005 | 22 | | PA | | 5-0 33-51-11 | D05010J | | 6 | | | | | D05708J | 7 | | | 150-199, 275-299 |
| 006R | 22 | | PH | | 5-0 26-11-12 | TB0286D | A004 | 2 | | | | | C00789 | 1 | D | | ALL |
| 007R | 24 | | PP | | 4-10 26-16-11 | TB0286D | A011 | 2 | | | | | C00772 | 1 | D | | ALL |
| 011 | 20 | | PA | | 12-3 33-11-13 | D07980P | | 25 | | | | | C01287 | 1 | D | | ALL |
| 012 | 24 | | PK | | 11-11 33-13-11 | D07982P | | 30 | | | | | C01246 | 1 | D | * | ALL |
| 013R | 22 | | PH | | 4-8 26-15-11 | TB0286D | A009 | 2 | | | | | C00776 | 1 | D | | ALL |
| 015 | 22 | | PA | | 12-0 33-16-12 | D07980P | | 21 | | | | | C01306 | 2 | D | | ALL |
| 019 | 16 | | PA | | 12-5 28-25-11 | D07980P | | 11 | FM | | | | C01058 | 1 | D | | ALL |
| 01A | 22 | | PA | | 10-11 21-28-11 | C00694 | | 2 | D | | | | D07980P | 5 | | | ALL |
| 01C | 22 | | PA | | 6-8 34-61-16 | C00725 | | 1 | D | | | | D04185J | 3 | | | 050-099, 275-299 |
| 01C | 22 | | PA | | 6-8 34-61-16 | C00725 | | 2 | D | | | | D04185J | 3 | | | 150-199 |
| 021 | 22 | | PA | | 7-7 29-11-32 | D05012J | | 1 | | | | | C01099 | 1 | D | | ALL |
| 023 | 20 | | PA | | 11-9 27-41-11 | D07980P | | 40 | | | | | C01528 | 2 | D | | ALL |
| 025R | 24 | | PP | | 11-3 26-16-11 | D07982P | | 7 | | | | | C00788 | 1 | D | | ALL |
| 029R | 22 | | PH | | 4-6 26-11-21 | TB0286D | A005 | 2 | | | | | C00775 | 1 | D | | ALL |
| 030R | 22 | | PH | | 11-0 26-11-21 | D07982P | | 4 | | | | | C00784 | 1 | D | | ALL |
| 031R | 22 | | PH | | 5-2 26-11-22 | TB0286D | A007 | 2 | | | | | C00791 | 1 | D | | ALL |
| 032R | 22 | | PH | | 11-7 26-11-22 | D07982P | | 5 | | | | | C00792 | 1 | D | | ALL |
| 033R | 22 | | PH | | 11-3 26-15-11 | D07980P | | 6 | | | | | C00785 | 1 | D | | ALL |
| 034R | 22 | | PH | | 11-9 26-15-12 | D07982P | | 1 | | | | | C00796 | 1 | D | | ALL |
| 036 | 24 | | PK | | 12-2 33-11-11 | D07982P | | 25 | | | | | C01283 | 1 | D | | ALL |
| 038 | 22 | | PQ | C | 12-1 33-16-12 | D07980P | | 22 | | | | | C01200 | 2 | D | | ALL |
| 038Z | | | | C | 0-0 33-16-12 | D07980P | | DED | | | | | C01200 | DED | | | ALL |
| 039 | 24 | | PK | | 11-4 27-58-21 | D07984P | | 19 | | | | | C01525 | 2 | D | | ALL |
| 040 | 22 | | PQ | D | 11-10 33-16-12 | D07982P | | 21 | | | | | C01308 | 2 | D | * | ALL |
| 040Z | | | | D | 0-0 33-16-12 | D07982P | | DED | | | | | C01308 | DED | | | ALL |
| 041 | 22 | | PQ | J | 11-10 33-16-17 | D07982P | | 24 | | | | | C01308 | 2 | D | * | ALL |
| 041Z | | | | J | 0-0 33-16-17 | D07982P | | DED | | | | | C01308 | DED | | | ALL |
| 042 | 16 | | PA | | 7-5 49-61-11 | D05012J | | 16 | FM | | | | C01391 | 1 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 15

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0044 | 286T0044 | | | P11-S2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 043R | 22 | | PH | 11-0 | 26-11-11 | D07980P | | 4 | | | | | C00783 | 1 | D | | ALL |
| 044R | 22 | | PH | 11-8 | 26-11-12 | D07980P | | 3 | | | | | C00790 | 1 | D | | ALL |
| 048 | 20 | | PA | 6-3 | 33-13-19 | L00505 | | =P | B | | | | SM00001 | | S | | ALL |
| 049 | 20 | | PA | 6-9 | 33-13-19 | L00503 | | =P | B | | | | D01600 | 9 | | | ALL |
| 050 | 20 | | PA | 5-4 | 33-13-19 | L00512 | | =P | B | | | | SM00002 | | S | | ALL |
| 051 | 20 | | PA | 4-4 | 33-13-19 | L00506 | | =P | B | | | | D01592 | 9 | | | ALL |
| 052 | 20 | | PA | 6-7 | 33-13-19 | L00519 | | =P | B | | | | SM00003 | | S | | ALL |
| 053 | 20 | | PA | 7-4 | 33-13-19 | L00513 | | =P | B | | | | D01520 | 9 | | | ALL |
| 054 | 20 | | PA | 3-1 | 33-13-19 | L00526 | | =P | B | | | | SM00001 | | S | | ALL |
| 055 | 20 | | PA | 4-1 | 33-13-19 | L00524 | | =P | B | | | | D01600 | 2 | | | ALL |
| 056 | 20 | | PA | 4-1 | 33-13-19 | L00533 | | =P | B | | | | SM00002 | | S | | ALL |
| 057 | 20 | | PA | 5-4 | 33-13-19 | L00527 | | =P | B | | | | D01592 | 2 | | | ALL |
| 058 | 20 | | PA | 6-0 | 33-13-19 | L00540 | | =P | B | | | | SM00003 | | S | | ALL |
| 059 | 20 | | PA | 7-5 | 33-13-19 | L00534 | | =P | B | | | | D01520 | 2 | | | ALL |
| 060 | 20 | | PA | 11-6 | 27-41-21 | D07982P | | | | | 40 | | C01529 | 2 | D | | ALL |
| 063 | 24 | | PK | 11-3 | 27-51-61 | D07984P | | | | | 14 | | C01037 | 2 | D | | ALL |
| 064 | 24 | | PK | 11-2 | 27-51-61 | D07984P | | | | | 15 | | C01025 | 2 | D | | ALL |
| 065 | 24 | | PK | 11-7 | 27-88-11 | D07984P | | | | | 12 | | C01001 | 2 | D | | ALL |
| 071 | 24 | | PK | 11-10 | 73-21-18 | D07980P | | | | | 33 | | C01427 | 1 | D | | ALL |
| 072 | 24 | | PK | 11-10 | 73-21-18 | D07980P | | | | | 34 | | C01426 | 1 | D | | ALL |
| 073 | 24 | | PV | A | 11-6 | 73-21-18 | D07982P | | | | 33 | | C01429 | 1 | D | | ALL |
| 073Z | | | A | | 0-0 | 73-21-18 | D07982P | | | | DED | | C01429 | DED | | | ALL |
| 074 | 24 | | PV | B | 11-5 | 73-21-18 | D07982P | | | | 34 | | C01428 | 1 | D | | ALL |
| 074Z | | | B | | 0-0 | 73-21-18 | D07982P | | | | DED | | C01428 | DED | | | ALL |
| 075 | 24 | | PK | | 4-9 | 21-33-21 | D05012J | | | | 8 | | C04205 | 1 | D | | ALL |
| 076 | 24 | | PK | | 4-10 | 21-33-21 | D05012J | | | | 9 | | C04206 | 1 | D | | ALL |
| 077 | 22 | | PA | | 6-2 | 34-12-11 | D04189J | | | | 30 | | C00625 | 2 | D | | ALL |
| 078 | 22 | | PA | | 6-0 | 34-12-11 | D04189J | | | | 32 | | C00002 | 2 | D | | ALL |
| 079 | 22 | | PA | | 6-1 | 34-12-11 | D04189J | | | | 33 | | C00001 | 2 | D | | ALL |
| 080 | 22 | | PA | | 6-3 | 34-12-11 | D04189J | | | | 34 | | C00001 | 1 | D | | ALL |
| 081 | 24 | | PK | | 12-1 | 73-21-15 | D07980P | | | | 39 | | C01512 | 1 | D | | ALL |
| 082 | 22 | | PA | | 5-3 | 33-13-19 | D01520 | | | | 12 | | SP02360 | | | 9 | ALL |
| 083 | 16 | | PA | | 5-1 | 33-13-19 | D01592 | | | | 11 | FM | GDX0001 | A.. | | 2 | ALL |
| 084 | 22 | | PA | | 5-3 | 33-13-19 | D01592 | | | | 12 | | SP02360 | | | 9 | ALL |
| 085 | 16 | | PA | | 4-4 | 33-13-19 | D01600 | | | | 11 | FM | GDX0001 | A.. | | 2 | ALL |
| 086 | 22 | | PA | | 3-7 | 33-13-19 | D01600 | | | | 12 | | SP02360 | | | 9 | ALL |
| 087 | 18 | | PA | | 1-9 | 33-13-19 | D01790 | | | | 2 | DK | SM00003 | | | S | ALL |
| 088 | 18 | | PA | | 1-10 | 33-13-19 | D01790 | | | | 8 | DK | SM00002 | | | S | ALL |
| 089 | 18 | | PA | | 1-10 | 33-13-19 | D01790 | | | | 9 | DK | SM00001 | | | S | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 16

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0044 | 286T0044 | | | P11-S2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | |
| 090 | 16 | PA | | 4-4 | 33-13-19 | D01790 | 11 | FM | | GDX0001 | A.. | 2 | | ALL | | |
| 091 | 22 | PA | | 3-7 | 33-13-19 | D01790 | 12 | | | SP02360 | | 9 | | ALL | | |
| 092 | 20 | PA | | 5-1 | 33-13-19 | D01520 | 7 | | | GDX0001 | S.. | 2 | | ALL | | |
| 093 | 20 | PA | | 5-1 | 33-13-19 | D01592 | 7 | | | GDX0001 | S.. | 2 | | ALL | | |
| 094 | 20 | PA | | 4-4 | 33-13-19 | D01600 | 7 | | | GDX0001 | S.. | 2 | | ALL | | |
| 095 | 20 | PA | | 4-4 | 33-13-19 | D01790 | 7 | | | GDX0001 | S.. | 2 | | ALL | | |
| 096 | 16 | PA | | 5-1 | 33-13-19 | D01520 | 11 | FM | | GDX0001 | A.. | 2 | | ALL | | |
| 135 | 20 | PA | | 4-8 | 21-31-31 | D05012J | 7 | | | C00683 | 1 | D | | ALL | | |
| 136 | 24 | PK | | 10-7 | 21-58-16 | D07984P | 31 | | | C00679 | 2 | D | | ALL | | |
| 138 | 24 | PK | | 11-9 | 73-21-14 | D07982P | 37 | | | C04153 | 1 | D | | ALL | | |
| 139 | 22 | PA | | 6-11 | 34-51-11 | D04185J | 1 | | | C00595 | 2 | D | | ALL | | |
| 140 | 22 | PA | | 6-3 | 23-51-21 | D04185J | 4 | | | SP01570 | | 9 | | ALL | | |
| 141 | 24 | PK | | 11-11 | 80-11-11 | D07982P | 39 | | | C01512 | 1 | D | | ALL | | |
| 142 | 24 | PK | | 5-1 | 31-51-11 | D04185J | 6 | | | C00567 | 1 | D | | ALL | | |
| 143 | 24 | PK | | 4-11 | 31-51-12 | D04189J | 17 | | | C00566 | 1 | D | | ALL | | |
| 144 | 22 | PA | | 7-3 | 23-42-11 | D04185J | 8 | | | C00551 | 2 | D | | ALL | | |
| 145 | 22 | PA | | 6-3 | 23-51-11 | D04185J | 9 | | | SP01568 | | 9 | | ALL | | |
| 146 | 18 | PA | | 4-11 | 27-11-22 | D04185J | 14 | | | C01030 | 2 | D | | ALL | | |
| 147 | 16 | PA | | 6-6 | 23-12-11 | D04185J | 16 | | | C00544 | 2 | D | | ALL | | |
| 148 | 18 | PA | | 7-1 | 23-31-11 | D04185J | 18 | | | C00548 | 2 | D | | ALL | | |
| 149 | 22 | PA | | 6-3 | 27-09-11 | D04189J | 2 | | | C01538 | 2 | D | | ALL | | |
| 150 | 22 | PA | | 6-2 | 27-09-11 | D04189J | 3 | | | C01534 | 2 | D | | ALL | | |
| 151 | 20 | PA | | 5-2 | 22-31-12 | D04189J | 4 | | | C00521 | 2 | D | | ALL | | |
| 152 | 20 | PA | | 5-2 | 22-11-32 | D04189J | 7 | | | C00521 | 2 | D | | ALL | | |
| 153 | 22 | PA | | 6-9 | 34-31-31 | D04189J | 8 | | | C00606 | 2 | D | | ALL | | |
| 154 | 24 | PK | | 6-6 | 34-22-81 | D04189J | 10 | | | C00635 | 2 | D | | ALL | | |
| 155 | 22 | PA | | 6-4 | 34-13-11 | D04189J | 11 | | | C00591 | 2 | D | | ALL | | |
| 156 | 22 | PA | | 6-2 | 23-51-11 | D04189J | 13 | | | SP01568 | | 9 | | ALL | | |
| 157 | 20 | PA | | 5-4 | 27-32-11 | D04189J | 14 | | | C01039 | 2 | D | | ALL | | |
| 159 | 24 | PK | | 6-3 | 34-24-11 | D04189J | 16 | | | C00604 | 2 | D | | ALL | | |
| 160 | 20 | PA | | 6-6 | 34-24-11 | D04189J | 18 | | | C00619 | 2 | D | | ALL | | |
| 161 | 18 | PA | | 4-11 | 27-11-12 | D04189J | 40 | | | C01026 | 2 | D | | ALL | | |
| 166 | 22 | PA | | 12-1 | 29-11-11 | D07980P | 15 | | | C01097 | 1 | D | | ALL | | |
| 167 | 22 | PA | | 6-7 | 33-51-11 | D05010J | 5 | | | C01212 | 1 | D | | ALL | | |
| 168 | 24 | PK | | 1-7 | 35-21-11 | D05010J | 12 | | | D05708J | 5 | | | 050-099 | | |
| 168 | 24 | PK | | 5-0 | 35-21-11 | D05010J | 12 | | | D05708J | 5 | | | 150-199, 275-299 | | |
| 169 | 22 | PQ | K | 11-7 | 76-11-11 | D07982P | 35 | | | C01419 | 1 | D | | ALL | | |
| 169Z | | | K | 0-0 | 76-11-11 | D07982P | DED | | | C01419 | DED | | | ALL | | |
| 170 | 24 | PK | | 11-6 | 32-42-11 | D07984P | 22 | | | C01183 | 2 | D | | ALL | | |

WIRE LIST

D280T132

91-21-11
 Section W0040
 Page 17
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0044 | 286T0044 | | | P11-S2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | |
| 171R | 22 | | | PH | 10-10 | 26-11-11 | D07980P | | | | C00793 | 1 | D | | ALL |
| 172 | 24 | | | PK | 11-6 | 32-42-11 | D07984P | | | | C01184 | 2 | D | | ALL |
| 175 | 22 | | | PQ | 5-2 | 74-31-21 | D05012J | | | | SP01468 | | 9 | | ALL |
| 175Z | | | | L | 0-0 | 74-31-21 | D05012J | | | DED | SP01468 | | DED | | ALL |
| 178 | 24 | | | PK | 6-5 | 74-31-11 | D05010J | | | | SP01986 | | 9 | | ALL |
| 179 | 18 | | | PA | 11-5 | 80-11-21 | D07980P | | | 38 | C01511 | 1 | D | | ALL |
| 180 | 20 | | | PA | 4-7 | 22-21-11 | D05012J | | | 6 | C01560 | 2 | D | | ALL |
| 181 | 22 | | | PA | 11-11 | 29-11-21 | D07982P | | | 15 | C01098 | 1 | D | | ALL |
| 183 | 22 | | | PA | 11-10 | 76-11-11 | D07980P | | | 35 | C01420 | 1 | D | | ALL |
| 185 | 22 | | | PA | 6-5 | 74-31-11 | D05010J | | | 21 | SP01474 | | 9 | | ALL |
| 186 | 24 | | | PK | 7-6 | 35-21-11 | D05708J | | | 1 | C01325 | 2 | D | | ALL |
| 187 | 24 | | | PK | 7-5 | 35-21-11 | D05708J | | | 2 | C01323 | 2 | D | | ALL |
| 188 | 16 | | | PA | 7-3 | 35-21-12 | D05708J | | | 14 | C01321 | 2 | D | | ALL |
| 189 | 16 | | | PA | 7-4 | 35-21-13 | D05708J | | | 16 | C01322 | 2 | D | | ALL |
| 190 | 16 | | | PA | 7-3 | 35-21-14 | D05708J | | | 18 | C01324 | 2 | D | | ALL |
| 191 | 22 | | | PA | 1-7 | 35-21-11 | D05708J | | | 6 | D05010J | 11 | | | 050-099 |
| 191 | 22 | | | PA | 5-0 | 35-21-11 | D05708J | | | 6 | D05010J | 11 | | | 150-199, 275-299 |
| 192 | 22 | | | PA | 3-6 | 23-51-21 | C00646 | | | 2 | TB0292F | A006 | 2 | | ALL |
| 193 | 22 | | | PA | 3-5 | 23-51-11 | C00644 | | | 2 | TB0292F | A007 | 2 | | ALL |
| 194 | 22 | | | PA | 6-1 | 27-09-11 | D04189J | | | 5 | C01537 | 2 | D | | ALL |
| 195 | 22 | | | PA | 6-0 | 27-09-11 | D04189J | | | 6 | C01533 | 2 | D | | ALL |
| 196 | 24 | | | PK | 2-7 | 24-51-31 | TB0292F | | | A003 | R00003 | = A | \$ | | ALL |
| 197 | 24 | | | PK | 7-6 | 24-51-31 | C00826 | | | 1 | TB0292F | A003 | 2 | | ALL |
| 199 | 22 | | | PA | 7-2 | 74-31-11 | C01435 | | | 1 | SP01472 | | 9 | | ALL |
| 300B | 24 | | | PM | 5-3 | 33-13-19 | D01520 | | | 5 | SP02364 | | 9 | | ALL |
| 300R | 24 | | | PM | 0-0 | 33-13-19 | D01520 | | | 6 | SP02362 | | 9 | | ALL |
| 300Y | 24 | | | PM | 0-0 | 33-13-19 | D01520 | | | 1 | SP02366 | | 9 | | ALL |
| 301B | 24 | | | PM | 5-3 | 33-13-19 | D01592 | | | 5 | SP02364 | | 9 | | ALL |
| 301R | 24 | | | PM | 0-0 | 33-13-19 | D01592 | | | 6 | SP02362 | | 9 | | ALL |
| 301Y | 24 | | | PM | 0-0 | 33-13-19 | D01592 | | | 1 | SP02366 | | 9 | | ALL |
| 302B | 24 | | | PM | 3-7 | 33-13-19 | D01600 | | | 5 | SP02364 | | 9 | | ALL |
| 302R | 24 | | | PM | 0-0 | 33-13-19 | D01600 | | | 6 | SP02362 | | 9 | | ALL |
| 302Y | 24 | | | PM | 0-0 | 33-13-19 | D01600 | | | 1 | SP02366 | | 9 | | ALL |
| 303B | 24 | | | PM | 3-7 | 33-13-19 | D01790 | | | 5 | SP02364 | | 9 | | ALL |
| 303R | 24 | | | PM | 0-0 | 33-13-19 | D01790 | | | 6 | SP02362 | | 9 | | ALL |
| 303Y | 24 | | | PM | 0-0 | 33-13-19 | D01790 | | | 1 | SP02366 | | 9 | | ALL |
| 510 | 22 | | | PQ | 9-0 | 28-22-31 | C01071 | | | 1 | D05010J | | 1 | | ALL |
| 510Z | | | | AC | 0-0 | 28-22-31 | C01071 | | | DED | D05010J | | DED | | ALL |
| 511 | 20 | | | PA | 11-8 | 78-34-11 | C01576 | | | 1 | D07980P | | 14 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 18

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0044 | 286T0044 | | | P11-S2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | | | |
| 512 | 20 | | PA | | 11-3 | 78-34-21 | C01577 | | 2 | D | | | | D07982P | 20 | | | | ALL |
| 700 | 20 | | PA | | 8-1 | 27-41-31 | C01010 | | 2 | D | | | | D04189J | 20 | | | | 050-099, 155-199, 275-299 |
| 704 | 24 | | PK | | 12-7 | 24-33-11 | D07984P | | 23 | | | | | C00892 | 1 | D | | | ALL |
| 705 | 24 | | PK | | 12-6 | 24-33-11 | D07984P | | 24 | | | | | C00811 | 1 | D | | | ALL |
| 707 | 22 | | PA | | 12-6 | 28-25-11 | D07980P | | 12 | | | | | C01052 | 1 | D | | | 050-099 |
| 707 | 20 | | PA | | 12-6 | 28-25-11 | D07980P | | 12 | | | | | C01052 | 1 | D | | | 150-199, 275-299 |
| 712 | 18 | | PQ | AA | 11-2 | 80-11-11 | D07982P | | 38 | DM | | | | C01510 | 1 | D | | | 050-099 |
| 712 | 18 | | PQ | AA | 11-2 | 80-11-11 | D07982P | | 38 | DK | | | | C01510 | 1 | D | | | 150-199, 275-299 |
| 712Z | | | | AA | 0-0 | 80-11-11 | D07982P | | DED | | | | | C01510 | DED | | | | ALL |
| 713 | 24 | | PK | | 1-0 | 24-51-31 | R00001 | | =C | | | | | R00002 | =C | | | * | ALL |
| 714 | 24 | | PK | | 4-2 | 24-51-31 | R00003 | | =C | | | | | R00002 | =C | | | * | 050-099 |
| 714 | 24 | | PK | | 4-2 | 24-51-31 | R00003 | | =C | | * | | | R00002 | =C | | | * | 150-199, 275-299 |
| 716 | 22 | | PA | | 6-9 | 34-57-21 | D04185J | | 5 | | | | | C00632 | 2 | D | | | 050-099 |
| 716 | 22 | | PA | | 6-9 | 34-57-21 | C00632 | | 2 | D | | | | D04185J | 5 | | | | 150-199, 275-299 |
| 723 | 20 | | PA | | 6-7 | 33-11-13 | D05010J | | 2 | | | | | SP02490 | | W | | | ALL |
| 724 | 20 | | PA | | 6-9 | 33-11-13 | GDX0001 | | D.. | 2 | | | | SP02492 | | W | | | ALL |
| 725 | 22 | | PA | | 2-3 | 23-51-11 | TB0292F | | A007 | 2 | | | | R00061 | =A | \$ | | | ALL |
| 726 | 22 | | PA | | 4-6 | 23-51-11 | R00061 | | =C | | | | | SP01568 | | 9 | | | ALL |
| 727 | 22 | | PA | | 2-3 | 23-51-21 | TB0292F | | A006 | 2 | | | | R00060 | =A | \$ | | | ALL |
| 728 | 22 | | PA | | 4-6 | 23-51-21 | R00060 | | =C | | | | | SP01570 | | 9 | | | ALL |
| 733 | 24 | | PK | | 6-9 | 33-11-15 | D05010J | | 3 | | | | | C01283 | 1 | D | | | ALL |
| 734 | 24 | | PK | | 5-4 | 24-51-31 | R00003 | | =C | | | | | TB5020 | 13 | E | | | 050-099 |
| 734 | 24 | | PK | | 5-4 | 24-51-31 | R00003 | | =C | | * | | | TB5020 | 13 | E | | | 150-199, 275-299 |
| 735R | 22 | | PH | | 11-7 | 26-17-11 | D07984P | | 6 | | | | | C00769 | 1 | D | | | ALL |
| 736R | 22 | | PH | | 11-7 | 26-17-11 | D07984P | | 7 | | | | | C00799 | 1 | D | | | ALL |
| 737 | 22 | | PA | | 6-6 | 33-13-16 | D05010J | | 9 | | | | | C01246 | 1 | D | | * | ALL |
| 738 | 18 | | PA | | 11-9 | 28-41-12 | D07982P | | 11 | DK | | | | C01048 | 2 | D | | | ALL |
| 739 | 20 | | PA | | 4-7 | 21-31-11 | D05012J | | 10 | | | | | C00658 | 1 | D | | | ALL |
| 740 | 24 | | PK | | 11-9 | 21-58-12 | D07984P | | 33 | | | | | C00688 | 1 | D | | | ALL |
| 745R | 22 | | PH | | 10-1 | 26-11-11 | D07984P | | 1 | | | | | TB0286D | C001 | 2 | | | ALL |
| 746R | 22 | | PH | | 10-1 | 26-11-12 | D07984P | | 3 | | | | | TB0286D | C004 | 2 | | | ALL |
| 747R | 22 | | PH | | 10-1 | 26-11-21 | D07984P | | 4 | | | | | TB0286D | C005 | 2 | | | ALL |
| 748R | 22 | | PH | | 10-1 | 26-11-22 | D07984P | | 5 | | | | | TB0286D | C007 | 2 | | | ALL |
| 749R | 22 | | PH | | 10-2 | 26-15-11 | D07982P | | 6 | | | | | TB0286D | C009 | 2 | | | ALL |
| 750R | 24 | | PP | | 10-5 | 26-16-11 | D07980P | | 7 | | | | | TB0286D | C011 | 2 | | | ALL |
| 751 | 20 | | PQ | M | 7-3 | 33-51-11 | C01310 | | 2 | D | | | | D05708J | 9 | | | | ALL |
| 751Z | | | | M | 0-0 | 33-51-11 | C01310 | | DED | | | | | D05708J | DED | | | | ALL |
| 752 | 20 | | PQ | N | 7-3 | 33-51-11 | C01303 | | 2 | D | | | | D05708J | 10 | | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 19

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0044 | 286T0044 | | | P11-S2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | |
| 752Z | | | | N | 0-0 | 33-51-11 | C01303 | | DED | | D05708J | | DED | | ALL |
| 753 | 22 | | PA | | 1-7 | 33-51-11 | D05010J | | 7 | | D05708J | | 11 | | 050-099 |
| 753 | 22 | | PA | | 5-0 | 33-51-11 | D05010J | | 7 | | D05708J | | 11 | | 150-199, 275-299 |
| A-A | | | | | 0-0 | 33-11-13 | L00707 | | A | | SP02490 | | | W | ALL |
| A-B | | | | | 0-0 | 33-11-13 | L00707 | | B | | SP02492 | | | W | ALL |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT | | | | | | | | | | | |
| 001 | 22 | | PA | | 4-0 | 31-51-11 | D00811 | | 60 | | GDX0001 | S.. | 2 | | ALL |
| 002 | 22 | | PA | | 4-0 | 31-51-11 | D00821 | | 14 | | GDX0002 | D.. | 2 | | ALL |
| 003 | 24 | | PV | AC | 5-0 | 31-51-11 | D00811 | | 26 | | D00821 | | 27 | | ALL |
| 003Z | | | | AC | 0-0 | 31-51-11 | D00811 | | DED | | D00821 | | | AC | ALL |
| 004 | 24 | | PV | AD | 5-0 | 31-51-11 | D00811 | | 49 | | D00821 | | 32 | | ALL |
| 004Z | | | | AD | 0-0 | 31-51-11 | D00811 | | DED | | D00821 | | | AC | ALL |
| 005 | 24 | | PV | AE | 5-0 | 31-51-11 | D00811 | | 35 | | D00821 | | 17 | | ALL |
| 005Z | | | | AE | 0-0 | 31-51-11 | D00811 | | DED | | D00821 | | | AC | ALL |
| 006 | 24 | | PK | | 3-0 | 31-51-11 | SM00022 | | | W | D00821 | | 51 | | ALL |
| 007 | 24 | | PK | | 4-0 | 31-51-11 | D00811 | | 65 | | SM00022 | | | W | ALL |
| 008 | 24 | | PK | | 3-0 | 31-51-11 | D00819 | | 37 | | SM00022 | | | W | ALL |
| 009 | 24 | | PV | AI | 4-0 | 31-51-11 | D00819 | | 27 | | D00811 | | 13 | | ALL |
| 009Z | | | | AI | 0-0 | 31-51-11 | D00811 | | DED | | D00819 | | | AI | ALL |
| 010 | 22 | | PA | | 3-0 | 31-51-11 | D00819 | | 14 | | GDX0001 | D.. | 2 | | ALL |
| 011 | 24 | | PK | | 3-0 | 31-51-11 | D01433 | | 51 | | SM00022 | | | W | ALL |
| 012 | 24 | | PV | AL | 4-0 | 31-51-11 | SM00018 | | | W | D01433 | | 27 | | ALL |
| 012Z | | | | AL | 0-0 | 31-51-11 | SM00018 | | REF | | D01433 | | | AL | ALL |
| 013 | 24 | | PV | AM | 3-0 | 31-51-11 | SM00047 | | | W | D01433 | | 32 | | ALL |
| 013Z | | | | AM | 0-0 | 31-51-11 | SM00047 | | REF | | D01433 | | | AL | ALL |
| 014 | 24 | | PV | AN | 4-0 | 31-51-11 | SM00049 | | | W | D01433 | | 17 | | ALL |
| 014Z | | | | AN | 0-0 | 31-51-11 | SM00049 | | REF | | D01433 | | | AL | ALL |
| 015 | 22 | | PA | | 3-0 | 31-51-11 | D01433 | | 14 | | GDX0001 | D.. | 2 | | ALL |
| 016 | 20 | | PA | | 0-10 | 31-51-11 | SM00028 | | | W | GDX0005 | D.. | 2 | | ALL |
| 017 | 20 | | UA | | 3-0 | 31-51-11 | GDX0002 | | S.. | 2 | D00821 | | | AC | ALL |
| 018 | 20 | | UA | | 3-0 | 31-51-11 | GDX0005 | | S.. | 2 | D00819 | | | AI | ALL |
| 019 | 20 | | UA | | 3-0 | 31-51-11 | D01433 | | | | GDX0002 | S.. | 2 | | ALL |
| 020 | 20 | | PA | | 0-10 | 31-51-11 | GDX0005 | | D.. | 2 | SM00029 | | | W | ALL |
| 021 | 20 | | UA | | 4-0 | 31-51-11 | GDX0002 | | S.. | 2 | D01503 | | | BB | ALL |
| 023 | 20 | | UA | | 3-0 | 31-51-11 | D00815 | | | | GDX0002 | S.. | 2 | | ALL |
| 024 | 24 | | PK | | 3-0 | 31-51-11 | D04349J | | 38 | | SM00005 | | | W | ALL |
| 025 | 24 | | PK | | 3-0 | 31-51-11 | D01503 | | A2 | | SM00005 | | | W | ALL |
| 026 | 20 | | PA | | 4-0 | 31-51-11 | D01503 | | A3 | | GDX0003 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 20

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | |
| 027 | 22 | | PQ | BB | 5-0 | 31-51-11 | D01503 | X2 | | | D00811 | 75 | | | ALL |
| 027Z | | | | BB | 0-0 | 31-51-11 | D00811 | DED | | | D01503 | | | BB | ALL |
| 028 | 24 | | PV | BC | 3-0 | 31-51-11 | D01503 | X1 | | | SM00015 | | W | | ALL |
| 028Z | | | | BC | 0-0 | 31-51-11 | SM00015 | REF | | BC | D01503 | | | BB | ALL |
| 029 | 24 | | PV | BD | 3-0 | 31-51-11 | D00811 | 46 | | | SM00015 | | W | | ALL |
| 029Z | | | | BD | 0-0 | 31-51-11 | SM00015 | REF | | BC | D00811 | DED | | | ALL |
| 030 | 24 | | PK | | 3-0 | 31-51-11 | SM00015 | | W | | D11553 | 35 | | | ALL |
| 032 | 20 | | PA | | 4-0 | 31-51-11 | D11553 | 11 | | | GD0003 | D.. | 2 | | ALL |
| 033 | 24 | | PK | | 5-0 | 31-51-11 | D11553 | 37 | | | D00811 | 34 | | | ALL |
| 034 | 24 | | PK | | 5-0 | 31-51-11 | D11553 | 36 | | | D00811 | 33 | | | ALL |
| 035 | 22 | | PA | | 4-0 | 31-51-11 | D00815 | 14 | | | GD0001 | D.. | 2 | | ALL |
| 036 | 24 | | PV | BK | 4-0 | 31-51-11 | D00815 | 27 | | | D00811 | 12 | | | ALL |
| 036Z | | | | BK | 0-0 | 31-51-11 | D00811 | DED | | | D00815 | | | BK | ALL |
| 037 | 24 | | PV | BL | 4-0 | 31-51-11 | D00815 | 32 | | | D00811 | 17 | | | ALL |
| 037Z | | | | BL | 0-0 | 31-51-11 | D00811 | DED | | | D00815 | | | BK | ALL |
| 038 | 24 | | PV | BM | 4-0 | 31-51-11 | D00815 | 17 | | | D00811 | 22 | | | ALL |
| 038Z | | | | BM | 0-0 | 31-51-11 | D00811 | DED | | | D00815 | | | BK | ALL |
| 039 | 24 | | PK | | 3-0 | 31-51-11 | D00815 | 54 | | | SM00020 | | W | | ALL |
| 040 | 24 | | PK | | 3-0 | 31-51-11 | D00811 | 63 | | | SM00020 | | W | | ALL |
| 041 | 24 | | PK | | 2-0 | 31-51-11 | D00823 | 35 | | | SM00020 | | W | | ALL |
| 042 | 24 | | PK | | 2-0 | 31-51-11 | D01381 | 35 | | | SM00020 | | W | | ALL |
| 045 | 22 | | PA | | 3-0 | 31-51-11 | D01381 | 14 | | | GD0001 | D.. | 2 | | ALL |
| 046 | 22 | | PA | | 3-0 | 31-51-11 | D01381 | 48 | | | GD0003 | D.. | 2 | | ALL |
| 047 | 24 | | PV | BV | 4-0 | 31-51-11 | D01381 | 27 | | | D00811 | 11 | | | ALL |
| 047Z | | | | BV | 0-0 | 31-51-11 | D00811 | DED | | | D01381 | | | BV | ALL |
| 048 | 24 | | PV | BW | 4-0 | 31-51-11 | D01381 | 32 | | | D00811 | 16 | | | ALL |
| 048Z | | | | BW | 0-0 | 31-51-11 | D00811 | DED | | | D01381 | | | BV | ALL |
| 049 | 24 | | PV | BX | 4-0 | 31-51-11 | D01381 | 17 | | | D00811 | 21 | | | ALL |
| 049Z | | | | BX | 0-0 | 31-51-11 | D00811 | DED | | | D01381 | | | BV | ALL |
| 052 | 22 | | PA | | 3-0 | 31-51-11 | D00823 | 14 | | | GD0001 | D.. | 2 | | ALL |
| 053 | 22 | | PA | | 3-0 | 31-51-11 | D00823 | 48 | | | GD0003 | D.. | 2 | | ALL |
| 054 | 24 | | PV | CD | 4-0 | 31-51-11 | D00823 | 27 | | | D00811 | 10 | | | ALL |
| 054Z | | | | CD | 0-0 | 31-51-11 | D00811 | DED | | | D00823 | | | CD | ALL |
| 055 | 24 | | PV | CE | 4-0 | 31-51-11 | D00823 | 32 | | | D00811 | 15 | | | ALL |
| 055Z | | | | CE | 0-0 | 31-51-11 | D00811 | DED | | | D00823 | | | CD | ALL |
| 056 | 24 | | PV | CF | 4-0 | 31-51-11 | D00823 | 17 | | | D00811 | 20 | | | ALL |
| 056Z | | | | CF | 0-0 | 31-51-11 | D00811 | DED | | | D00823 | | | CD | ALL |
| 057 | 22 | | PA | | 4-0 | 31-51-11 | D00817 | 14 | | | GD0002 | D.. | 2 | | ALL |
| 058 | 24 | | PV | CH | 5-0 | 31-51-11 | D00817 | 27 | | | D00811 | 51 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0040
 Page 21
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | | | |
| 058Z | | | CH | 0-0 | 31-51-11 | D00811 | | DED | | | | | D00817 | | | CH | ALL |
| 059 | 24 | PV | CI | 5-0 | 31-51-11 | D00817 | | 32 | | | | | D00811 | 74 | | | ALL |
| 059Z | | | CI | 0-0 | 31-51-11 | D00811 | | DED | | | | | D00817 | | | CH | ALL |
| 060 | 24 | PK | | 3-0 | 31-51-11 | D00817 | | 45 | | | | | SM00021 | | W | | ALL |
| 061 | 24 | PK | | 3-0 | 31-51-11 | D00811 | | 64 | | | | | SM00021 | | W | | ALL |
| 062 | 24 | PK | | 3-0 | 31-51-11 | D01489 | | 16 | | | | | SM00021 | | W | | ALL |
| 063 | 24 | PK | | 3-0 | 31-51-11 | D01487 | | 45 | | | | | SM00021 | | W | | ALL |
| 064 | 24 | PV | CN | 5-0 | 31-51-11 | D01487 | | 27 | | | | | D00811 | 47 | | | ALL |
| 064Z | | | CN | 0-0 | 31-51-11 | D00811 | | DED | | | | | D01487 | | | CN | ALL |
| 065 | 24 | PV | CO | 5-0 | 31-51-11 | D01487 | | 32 | | | | | D00811 | 70 | | | ALL |
| 065Z | | | CO | 0-0 | 31-51-11 | D00811 | | DED | | | | | D01487 | | | CN | ALL |
| 066 | 22 | PA | | 4-0 | 31-51-11 | D01487 | | 14 | | | | | GDX0003 | D.. | 2 | | ALL |
| 067 | 24 | PV | CQ | 5-0 | 31-51-11 | D01489 | | 27 | | | | | D00811 | 45 | | | ALL |
| 067Z | | | CQ | 0-0 | 31-51-11 | D00811 | | DED | | | | | D01489 | | | CQ | ALL |
| 068 | 24 | PV | CR | 5-0 | 31-51-11 | D01489 | | 32 | | | | | D00811 | 50 | | | ALL |
| 068Z | | | CR | 0-0 | 31-51-11 | D00811 | | DED | | | | | D01489 | | | CQ | ALL |
| 069 | 24 | PV | CS | 5-0 | 31-51-11 | D01489 | | 17 | | | | | D00811 | 36 | | | ALL |
| 069Z | | | CS | 0-0 | 31-51-11 | D00811 | | DED | | | | | D01489 | | | CQ | ALL |
| 070 | 22 | PA | | 4-0 | 31-51-11 | D01489 | | 14 | | | | | GDX0003 | D.. | 2 | | ALL |
| 071 | 20 | UA | | 3-0 | 31-51-11 | D01381 | | | | | BV | | GDX0002 | S.. | 2 | | ALL |
| 072 | 20 | UA | | 3-0 | 31-51-11 | D00823 | | | | | CD | | GDX0002 | S.. | 2 | | ALL |
| 073 | 20 | UA | | 3-0 | 31-51-11 | D00817 | | | | | CH | | GDX0002 | S.. | 2 | | ALL |
| 074 | 20 | PA | | 0-10 | 31-51-11 | SM00026 | | | W | | | | GDX0005 | D.. | 2 | | ALL |
| 075 | 20 | UA | | 4-0 | 31-51-11 | D01487 | | | | | CN | | GDX0005 | S.. | 2 | | ALL |
| 076 | 20 | UA | | 4-0 | 31-51-11 | GDX0005 | | S.. | 2 | | | | D01489 | | | CQ | ALL |
| 077 | 24 | PK | | 4-0 | 31-41-35 | D02261 | | 40 | | | | | D04349J | 1 | | | ALL |
| 078 | 20 | PA | | 0-10 | 31-51-11 | SM00027 | | | W | | | | GDX0005 | D.. | 2 | | ALL |
| 079 | 22 | PA | | 4-0 | 31-51-12 | D00813 | | 60 | | | | | GDX0003 | S.. | 2 | | ALL |
| 080 | 22 | PA | | 4-0 | 31-51-12 | D00821 | | 15 | | | | | GDX0002 | D.. | 2 | | ALL |
| 081 | 24 | PV | DF | 5-0 | 31-51-12 | D00821 | | 30 | | | | | D00813 | 26 | | | ALL |
| 081Z | | | DF | 0-0 | 31-51-12 | D00813 | | DED | | | | | D00821 | | | DF | ALL |
| 082 | 24 | PV | DG | 5-0 | 31-51-12 | D00821 | | 33 | | | | | D00813 | 49 | | | ALL |
| 082Z | | | DG | 0-0 | 31-51-12 | D00813 | | DED | | | | | D00821 | | | DF | ALL |
| 083 | 24 | PV | DH | 5-0 | 31-51-12 | D00821 | | 24 | | | | | D00813 | 35 | | | ALL |
| 083Z | | | DH | 0-0 | 31-51-12 | D00813 | | DED | | | | | D00821 | | | DF | ALL |
| 084 | 24 | PK | | 3-0 | 31-51-12 | D00821 | | 19 | | | | | SM00025 | | W | | ALL |
| 085 | 24 | PK | | 4-0 | 31-51-12 | D00813 | | 65 | | | | | SM00025 | | W | | ALL |
| 086 | 24 | PK | | 3-0 | 31-51-12 | D00819 | | 3 | | | | | SM00025 | | W | | ALL |
| 087 | 24 | PK | | 2-0 | 31-51-12 | D01433 | | 18 | | | | | SM00025 | | W | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 22

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | | | |
| 088 | 22 | | PA | | 3-0 | 31-51-12 | D01433 | | 15 | | | | GDX0002 | D.. | 2 | | ALL |
| 089 | 24 | | PV | DN | 5-0 | 31-51-12 | D01433 | | 30 | | | | SM00054 | | W | | ALL |
| 089Z | | | | DN | 0-0 | 31-51-12 | SM00054 | | REF | | Y0 | | D01433 | | | DN | ALL |
| 090 | 24 | | PV | DO | 5-0 | 31-51-12 | D01433 | | 33 | | | | SM00055 | | W | | ALL |
| 090Z | | | | DO | 0-0 | 31-51-12 | SM00055 | | REF | | Y1 | | D01433 | | | DN | ALL |
| 091 | 24 | | PV | DP | 5-0 | 31-51-12 | D01433 | | 24 | | | | SM00056 | | W | | ALL |
| 091Z | | | | DP | 0-0 | 31-51-12 | SM00056 | | REF | | Y2 | | D01433 | | | DN | ALL |
| 092 | 22 | | PA | | 3-0 | 31-51-12 | D00819 | | 15 | | | | GDX0002 | D.. | 2 | | ALL |
| 093 | 24 | | PV | DR | 4-0 | 31-51-12 | D00819 | | 30 | | | | D00813 | | 13 | | ALL |
| 093Z | | | | DR | 0-0 | 31-51-12 | D00813 | | DED | | | | D00819 | | | DR | ALL |
| 094 | 20 | | PA | | 0-10 | 31-51-12 | SM00032 | | | W | | | GDX0005 | D.. | 2 | | ALL |
| 095 | 24 | | PV | DT | 5-0 | 31-51-12 | D01505 | | X2 | | | | D00813 | | 75 | | ALL |
| 095Z | | | | DT | 0-0 | 31-51-12 | D00813 | | DED | | | | D01505 | | | DT | ALL |
| 096 | 24 | | PV | DU | 3-0 | 31-51-12 | D01505 | | X1 | | | | SM00016 | | W | | ALL |
| 096Z | | | | DU | 0-0 | 31-51-12 | SM00016 | | REF | | DU | | D01505 | | | DT | ALL |
| 097 | 24 | | PV | DV | 4-0 | 31-51-12 | D00813 | | 46 | | | | SM00016 | | W | | ALL |
| 097Z | | | | DV | 0-0 | 31-51-12 | SM00016 | | REF | | DU | | D00813 | DED | | | ALL |
| 098 | 20 | | PA | | 0-10 | 31-51-12 | SM00033 | | | W | | | GDX0005 | D.. | 2 | | ALL |
| 099 | 24 | | PK | | 3-0 | 31-51-12 | SM00016 | | | W | | | D11553 | | 25 | | ALL |
| 100 | 20 | | PA | | 4-0 | 31-51-12 | D11553 | | 1 | | | | GDX0003 | D.. | 2 | | ALL |
| 101 | 20 | | UA | | 4-0 | 31-51-12 | D00821 | | | | DF | | GDX0004 | S.. | 2 | | ALL |
| 102 | 20 | | UA | | 3-0 | 31-51-12 | D00819 | | | | DR | | GDX0004 | S.. | 2 | | ALL |
| 103 | 20 | | UA | | 3-0 | 31-51-12 | D01433 | | | | DN | | GDX0004 | S.. | 2 | | ALL |
| 104 | 20 | | UA | | 4-0 | 31-51-12 | D01505 | | | | DT | | GDX0005 | S.. | 2 | | ALL |
| 106 | 20 | | UA | | 3-0 | 31-51-12 | D00815 | | | | FS | | GDX0004 | S.. | 2 | | ALL |
| 107 | 20 | | UA | | 3-0 | 31-51-12 | D01381 | | | | FF | | GDX0004 | S.. | 2 | | ALL |
| 109 | 20 | | UA | | 4-0 | 31-51-12 | D00817 | | | | FD | | GDX0004 | S.. | 2 | | ALL |
| 110 | 20 | | UA | | 4-0 | 31-51-12 | D01487 | | | | FJ | | GDX0001 | S.. | 2 | | ALL |
| 111 | 20 | | UA | | 4-0 | 31-51-12 | D01489 | | | | FM | | GDX0001 | S.. | 2 | | ALL |
| 112 | 22 | | PA | | 4-0 | 31-51-12 | D00815 | | 15 | | | | GDX0001 | D.. | 2 | | ALL |
| 113 | 24 | | PK | | 3-0 | 31-51-12 | D01505 | | A2 | | | | SM00005 | | W | | ALL |
| 114 | 20 | | PA | | 4-0 | 31-51-12 | D01505 | | A3 | | | | GDX0003 | D.. | 2 | | ALL |
| 115 | 24 | | PK | | 4-0 | 21-61-51 | D02261 | | 21 | | | | D04347J | | 25 | | ALL |
| 116 | 24 | | PK | | 3-0 | 31-51-12 | D00815 | | 21 | | | | SM00023 | | W | | ALL |
| 117 | 24 | | PK | | 4-0 | 31-51-12 | D00813 | | 63 | | | | SM00023 | | W | | ALL |
| 118 | 24 | | PK | | 2-0 | 31-51-12 | D00823 | | 1 | | | | SM00023 | | W | | ALL |
| 119 | 24 | | PK | | 2-0 | 31-51-12 | D01381 | | 1 | | | | SM00023 | | W | | ALL |
| 120 | 22 | | PA | | 3-0 | 31-51-12 | D01381 | | 15 | | | | GDX0001 | D.. | 2 | | ALL |
| 121 | 24 | | PK | | 3-0 | 31-51-12 | D00817 | | 56 | | | | SM00024 | | W | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0040
Page 23
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | | | |
| 122 | 24 | | PK | 4-0 | 31-51-12 | D00813 | | 64 | | | | | SM00024 | | W | | ALL |
| 123 | 24 | | PK | 3-0 | 31-51-12 | D01487 | | 56 | | | | | SM00024 | | W | | ALL |
| 124 | 22 | | PA | 3-0 | 31-51-12 | D00823 | | 15 | | | | | GDX0001 | D.. | 2 | | ALL |
| 125 | 20 | | UA | 3-0 | 31-51-12 | D00823 | | | | FA | | | GDX0004 | S.. | 2 | | ALL |
| 126 | 24 | | PV | 5-0 | 31-51-12 | D00823 | | 33 | | | | | D00813 | 15 | | | ALL |
| 126Z | | | FA | 0-0 | 31-51-12 | D00823 | | | | FA | | | D00813 | DED | | | ALL |
| 127 | 24 | | PV | 5-0 | 31-51-12 | D00823 | | 24 | | | | | D00813 | 20 | | | ALL |
| 127Z | | | FB | 0-0 | 31-51-12 | D00823 | | | | FA | | | D00813 | DED | | | ALL |
| 128 | 22 | | PA | 4-0 | 31-51-12 | D00817 | | 15 | | | | | GDX0002 | D.. | 2 | | ALL |
| 129 | 24 | | PV | 5-0 | 31-51-12 | D00817 | | 30 | | | | | D00813 | 51 | | | ALL |
| 129Z | | | FD | 0-0 | 31-51-12 | D00817 | | | | FD | | | D00813 | DED | | | ALL |
| 130 | 24 | | PV | 5-0 | 31-51-12 | D00817 | | 33 | | | | | D00813 | 74 | | | ALL |
| 130Z | | | FE | 0-0 | 31-51-12 | D00817 | | | | FD | | | D00813 | DED | | | ALL |
| 131 | 24 | | PV | 5-0 | 31-51-12 | D00813 | | 11 | | | | | D01381 | 30 | | | ALL |
| 131Z | | | FF | 0-0 | 31-51-12 | D01381 | | | | FF | | | D00813 | DED | | | ALL |
| 132 | 24 | | PV | 5-0 | 31-51-12 | D00813 | | 16 | | | | | D01381 | 33 | | | ALL |
| 132Z | | | FG | 0-0 | 31-51-12 | D01381 | | | | FF | | | D00813 | DED | | | ALL |
| 133 | 24 | | PV | 5-0 | 31-51-12 | D01381 | | 24 | | | | | D00813 | 21 | | | ALL |
| 133Z | | | FH | 0-0 | 31-51-12 | D01381 | | | | FF | | | D00813 | DED | | | ALL |
| 134 | 24 | | PK | 3-0 | 31-51-12 | D01489 | | 50 | | | | | SM00024 | | W | | ALL |
| 135 | 24 | | PV | 5-0 | 31-51-12 | D01487 | | 30 | | | | | D00813 | 47 | | | ALL |
| 135Z | | | FJ | 0-0 | 31-51-12 | D01487 | | | | FJ | | | D00813 | DED | | | ALL |
| 136 | 24 | | PV | 5-0 | 31-51-12 | D01487 | | 33 | | | | | D00813 | 70 | | | ALL |
| 136Z | | | FK | 0-0 | 31-51-12 | D01487 | | | | FJ | | | D00813 | DED | | | ALL |
| 137 | 22 | | PA | 4-0 | 31-51-12 | D01487 | | 15 | | | | | GDX0003 | D.. | 2 | | ALL |
| 138 | 24 | | PV | 5-0 | 31-51-12 | D01489 | | 30 | | | | | D00813 | 45 | | | ALL |
| 138Z | | | FM | 0-0 | 31-51-12 | D01489 | | | | FM | | | D00813 | DED | | | ALL |
| 139 | 24 | | PV | 5-0 | 31-51-12 | D01489 | | 33 | | | | | D00813 | 50 | | | ALL |
| 139Z | | | FN | 0-0 | 31-51-12 | D01489 | | | | FM | | | D00813 | DED | | | ALL |
| 140 | 24 | | PV | 5-0 | 31-51-12 | D01489 | | 24 | | | | | D00813 | 36 | | | ALL |
| 140Z | | | FO | 0-0 | 31-51-12 | D01489 | | | | FM | | | D00813 | DED | | | ALL |
| 141 | 22 | | PA | 4-0 | 31-51-12 | D01489 | | 15 | | | | | GDX0003 | D.. | 2 | | ALL |
| 142 | 24 | | PK | 6-0 | 31-51-12 | D00813 | | 33 | | | | | D11553 | 26 | | | ALL |
| 143 | 24 | | PK | 6-0 | 31-51-12 | D11553 | | 27 | | | | | D00813 | 34 | | | ALL |
| 144 | 24 | | PV | 5-0 | 31-51-12 | D00813 | | 12 | | | | | D00815 | 30 | | | ALL |
| 144Z | | | FS | 0-0 | 31-51-12 | D00813 | | DED | | | | | D00815 | | | FS | ALL |
| 145 | 20 | | PA | 0-10 | 31-51-12 | SM00030 | | | W | | | | GDX0005 | D.. | 2 | | ALL |
| 146 | 24 | | PV | 5-0 | 31-51-12 | D00813 | | 17 | | | | | D00815 | 33 | | | ALL |
| 146Z | | | FU | 0-0 | 31-51-12 | D00813 | | DED | | | | | D00815 | | | FS | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 24

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|---|-------|-------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0045 | 286T0045 | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | | | |
| 147 | 24 | PV | FV | 5-0 | 31-51-12 | D00813 | | 22 | | | D00815 | 24 | | | ALL |
| 147Z | | | FV | 0-0 | 31-51-12 | D00813 | | DED | | | D00815 | | | FS | ALL |
| 148 | 24 | PV | FW | 5-0 | 31-51-12 | D00813 | | 10 | | | D00823 | 30 | | | ALL |
| 148Z | | | FW | 0-0 | 31-51-12 | D00813 | | DED | | | D00823 | | | FA | ALL |
| 149 | 20 | PA | | 0-10 | 31-51-12 | SM00031 | | | W | | GDX0005 | D.. | 2 | | ALL |
| 150 | 22 | PA | | 4-0 | 27-32-11 | D04301J | | 6 | | | D00823 | 34 | | | ALL |
| 151 | 24 | PK | | 3-0 | 27-32-11 | D04509J | | 1 | | | D00823 | 39 | | | ALL |
| 152 | 24 | PK | | 4-0 | 27-32-11 | D04347J | | 26 | | | D00823 | 40 | | | ALL |
| 153 | 24 | PK | | 3-0 | 27-32-11 | D00823 | | 31 | | | D04509J | 6 | | | ALL |
| 154 | 20 | PA | | 4-0 | 27-32-11 | D04509J | | 7 | | | GDX0001 | D.. | 2 | | ALL |
| 155 | 24 | PK | | 3-0 | 27-32-11 | SM00037 | | | W | | D04511J | 3 | | | ALL |
| 156 | 24 | PK | | 4-0 | 27-32-11 | D00823 | | 38 | | | D04511J | 2 | | | ALL |
| 157 | 24 | PK | | 4-0 | 27-32-11 | D04511J | | 4 | | | SM00050 | | W | | ALL |
| 158 | 24 | PK | | 2-0 | 27-32-11 | SM00037 | | | W | | D00823 | 4 | | | ALL |
| 159 | 24 | PK | | 4-0 | 27-32-11 | D04349J | | 14 | | | D00823 | 36 | | | ALL |
| 160 | 24 | PK | | 4-0 | 27-32-11 | D04349J | | 15 | | | D00823 | 3 | | | ALL |
| 161 | 24 | PK | | 4-0 | 27-32-11 | D04349J | | 16 | | | D00823 | 43 | | | ALL |
| 162 | 24 | PK | | 4-0 | 27-32-11 | D04349J | | 10 | | | D00823 | 2 | | | ALL |
| 165 | 22 | PA | | 4-0 | 27-32-21 | D04349J | | 11 | | | D01381 | 34 | | | ALL |
| 166 | 24 | PK | | 4-0 | 27-32-21 | D01381 | | 40 | | | D04349J | 6 | | | ALL |
| 167 | 24 | PK | | 4-0 | 27-32-21 | D01381 | | 31 | | | D04511J | 7 | | | ALL |
| 168 | 20 | PA | | 4-0 | 27-32-21 | GDX0002 | | D.. | 2 | | D04511J | 8 | | | ALL |
| 169 | 24 | PK | | 4-0 | 27-32-21 | D04349J | | 34 | | | D01381 | 36 | | | ALL |
| 170 | 24 | PK | | 4-0 | 27-32-21 | D04349J | | 35 | | | D01381 | 3 | | | ALL |
| 171 | 24 | PK | | 4-0 | 27-32-21 | D04349J | | 36 | | | D01381 | 43 | | | ALL |
| 172 | 24 | PK | | 4-0 | 27-32-21 | D04349J | | 37 | | | D01381 | 2 | | | ALL |
| 173 | 24 | PK | | 4-0 | 27-32-21 | D04511J | | 13 | | | D01381 | 4 | | | ALL |
| 174 | 24 | PK | | 4-0 | 27-32-21 | D04511J | | 16 | | | D01381 | 37 | | | ALL |
| 175 | 24 | PK | | 4-0 | 27-32-21 | D04511J | | 15 | | | D01381 | 38 | | | ALL |
| 176 | 24 | PK | | 4-0 | 27-32-21 | D04509J | | 8 | | | D01381 | 39 | | | ALL |
| 177 | 24 | PK | | 4-0 | 31-51-21 | D00815 | | 34 | | | SM00057 | | W | | ALL |
| 178 | 24 | PK | | 4-0 | 31-51-21 | D00815 | | 43 | | | D01433 | 19 | | | ALL |
| 179 | 24 | PK | | 3-0 | 31-51-21 | D00815 | | 10 | | | D00819 | 5 | | | ALL |
| 180 | 24 | PK | | 3-0 | 31-51-21 | D04507J | | 5 | | | SM00034 | | W | | ALL |
| 181 | 24 | PK | | 5-0 | 31-51-21 | SM00058 | | | W | | D00815 | 66 | | | ALL |
| 182 | 24 | PK | | 3-0 | 31-51-21 | D00815 | | 4 | | | SM00034 | | W | | ALL |
| 183 | 24 | PK | | 5-0 | 31-51-21 | D00815 | | 11 | | | D04349J | 39 | | | ALL |
| 184 | 22 | PA | | 3-0 | 31-51-21 | D00815 | | 37 | | | SM00035 | | W | | ALL |
| 185 | 22 | PA | | 3-0 | 31-51-21 | D00815 | | 42 | | | SM00036 | | W | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 25

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | | | |
| 186 | 24 | | PK | 3-0 | 31-51-21 | D04349J | | 5 | | | | | SM00012 | | W | | ALL |
| 187 | 24 | | PK | 3-0 | 31-51-21 | D00815 | | 2 | | | | | SM00012 | | W | | ALL |
| 188 | 24 | | PK | 3-0 | 31-51-21 | SM00011 | | | W | | | | D04349J | 4 | | | ALL |
| 189 | 24 | | PK | 3-0 | 31-51-21 | SM00011 | | | W | | | | D00815 | 35 | | | ALL |
| 190 | 24 | | PK | 3-0 | 31-51-21 | D04349J | | 12 | | | | | SM00009 | | W | | ALL |
| 191 | 24 | | PK | 3-0 | 31-51-21 | D00815 | | 44 | | | | | SM00009 | | W | | ALL |
| 192 | 24 | | PK | 3-0 | 31-51-21 | D04347J | | 10 | | | | | SM00008 | | W | | ALL |
| 193 | 24 | | PK | 3-0 | 31-51-21 | D00815 | | 1 | | | | | SM00008 | | W | | ALL |
| 194 | 24 | | PK | 3-0 | 31-51-21 | D04347J | | 11 | | | | | SM00010 | | W | | ALL |
| 195 | 24 | | PK | 3-0 | 31-51-21 | D00815 | | 36 | | | | | SM00010 | | W | | ALL |
| 196 | 24 | | PK | 3-0 | 31-51-21 | SM00039 | | | W | | | | D04347J | 21 | | | ALL |
| 197 | 24 | | PK | 3-0 | 31-51-21 | D00815 | | 45 | | | | | SM00039 | | W | | ALL |
| 198 | 24 | | PK | 5-0 | 31-51-21 | D00815 | | 46 | | | | | D04347J | 6 | | | ALL |
| 199 | 20 | | PA | 4-0 | 31-51-31 | GDX0004 | | S.. | 2 | | | | D04597J | 14 | | | ALL |
| 201B | 24 | | PW | IA | 4-0 | 31-51-33 | D01489 | | | | | | SM00004 | | W | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 31-51-33 | D01489 | | 9 | | | | SM00003 | | W | | ALL |
| 201Z | | | | IA | 0-0 | 31-51-33 | D01489 | | DED | | | | SM00003 | REF | | IA | ALL |
| 204 | 20 | | UA | | 4-0 | 27-32-11 | D04507J | | | | ID | | GDX0004 | S.. | 2 | | ALL |
| 204B | 24 | | PW | ID | 3-0 | 27-32-11 | D00823 | | 18 | | | | D04507J | 12 | | | ALL |
| 204R | 24 | | PW | ID | 0-0 | 27-32-11 | D00823 | | 16 | | | | D04507J | 11 | | | ALL |
| 204Z | | | | ID | 0-0 | 27-32-11 | D04507J | | | | ID | | D00823 | DED | | | ALL |
| 205B | 24 | | PW | IE | 3-0 | 31-51-21 | D00815 | | 19 | | | | SM00007 | | W | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 31-51-21 | D00815 | | 52 | | | | SM00006 | | W | | ALL |
| 205Z | | | | IE | 0-0 | 31-51-21 | D00815 | | DED | | | | SM00006 | REF | | IE | ALL |
| 207 | 20 | | UA | | 4-0 | 31-51-21 | D04597J | | | | IG | | GDX0004 | S.. | 2 | | ALL |
| 207B | 24 | | PW | IG | 3-0 | 31-51-21 | SM00007 | | | W | | | D04597J | 4 | | | ALL |
| 207R | 24 | | PW | IG | 0-0 | 31-51-21 | SM00006 | | | W | | | D04597J | 3 | | | ALL |
| 207Z | | | | IG | 0-0 | 31-51-21 | SM00006 | | REF | | IE | | D04597J | | | IG | ALL |
| 208 | 20 | | UA | | 4-0 | 34-16-11 | D04301J | | | | IH | | GDX0002 | S.. | 2 | | ALL |
| 208B | 24 | | PW | IH | 4-0 | 34-16-11 | D00821 | | 36 | | | | D04301J | 9 | | | ALL |
| 208R | 24 | | PW | IH | 0-0 | 34-16-11 | D00821 | | 2 | | | | D04301J | 8 | | | ALL |
| 208Z | | | | IH | 0-0 | 34-16-11 | D00821 | | DED | | | | D04301J | | | IH | ALL |
| 209B | 24 | | PW | II | 4-0 | 31-51-33 | D01489 | | 46 | | | | SM00007 | | W | | ALL |
| 209R | 24 | | PW | II | 0-0 | 31-51-33 | D01489 | | 12 | | | | SM00006 | | W | | ALL |
| 209Z | | | | II | 0-0 | 31-51-33 | D01489 | | DED | | | | SM00006 | REF | | IE | ALL |
| 212B | 24 | | PW | IL | 2-0 | 31-51-42 | D01433 | | 36 | | | | SM00007 | | W | | ALL |
| 212R | 24 | | PW | IL | 0-0 | 31-51-42 | D01433 | | 2 | | | | SM00006 | | W | | ALL |
| 212Z | | | | IL | 0-0 | 31-51-42 | D01433 | | DED | | | | SM00006 | REF | | IE | ALL |
| 213 | 20 | | UA | | 4-0 | 34-16-11 | D04507J | | | | IM | | GDX0004 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 26

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | | |
| 213B | 24 | PW | IM | | 4-0 | 34-16-11 | D00821 | | 35 | | | D04507J | | 8 | | ALL |
| 213R | 24 | PW | IM | | 0-0 | 34-16-11 | D00821 | | 1 | | | D04507J | | 9 | | ALL |
| 213Z | | | IM | | 0-0 | 34-16-11 | D00821 | | DED | | | D04507J | | | IM | ALL |
| 214 | 20 | UA | | | 4-0 | 34-16-11 | D04349J | | | IN | | GDX0004 | S.. | 2 | | ALL |
| 214B | 24 | PW | IN | | 4-0 | 34-16-11 | D00821 | | 37 | | | D04349J | | 19 | | ALL |
| 214R | 24 | PW | IN | | 0-0 | 34-16-11 | D00821 | | 3 | | | D04349J | | 18 | | ALL |
| 214Z | | | IN | | 0-0 | 34-16-11 | D00821 | | DED | | | D04349J | | | IN | ALL |
| 215B | 24 | PL | IO | | 4-0 | 31-51-31 | D01487 | | 24 | | | D04597J | | 12 | | ALL |
| 215R | 24 | PL | IO | | 0-0 | 31-51-31 | D01487 | | 23 | | | D04597J | | 13 | | ALL |
| 216B | 24 | PL | IP | | 4-0 | 31-51-32 | D00817 | | 24 | | | D04303J | | 12 | | ALL |
| 216R | 24 | PL | IP | | 0-0 | 31-51-32 | D00817 | | 23 | | | D04303J | | 11 | | ALL |
| 221B | 24 | PW | IU | | 4-0 | 31-51-33 | D01489 | | 45 | | | SM00004 | | | W | ALL |
| 221R | 24 | PW | IU | | 0-0 | 31-51-33 | D01489 | | 11 | | | SM00003 | | | W | ALL |
| 221Z | | | IU | | 0-0 | 31-51-33 | D01489 | | DED | | | SM00003 | REF | | IA | ALL |
| 223B | 24 | PW | IW | | 3-0 | 34-16-11 | D00821 | | 38 | | | SM00004 | | | W | ALL |
| 223R | 24 | PW | IW | | 0-0 | 34-16-11 | D00821 | | 4 | | | SM00003 | | | W | ALL |
| 223Z | | | IW | | 0-0 | 34-16-11 | D00821 | | DED | | | SM00003 | REF | | IA | ALL |
| 224 | 20 | UA | | | 4-0 | 27-32-21 | D04349J | | | IX | | GDX0004 | S.. | 2 | | ALL |
| 224B | 24 | PW | IX | | 3-0 | 27-32-21 | D04349J | | 28 | | | D01381 | | 18 | | ALL |
| 224R | 24 | PW | IX | | 0-0 | 27-32-21 | D04349J | | 27 | | | D01381 | | 16 | | ALL |
| 224Z | | | IX | | 0-0 | 27-32-21 | D04349J | | | IX | | D01381 | DED | | | ALL |
| 225B | 22 | PR | IY | | 3-0 | 31-51-11 | D00811 | | 69 | | | SM00060 | | | W | ALL |
| 225R | 22 | PR | IY | | 0-0 | 31-51-11 | D00811 | | 68 | | | SM00060 | | | W | ALL |
| 225Z | | | IY | | 0-0 | 31-51-11 | D00811 | | DED | | | SM00028 | REF | | MA | ALL |
| 226B | 22 | PR | JA | | 4-0 | 31-51-12 | D00813 | | 69 | | | SM00061 | | | W | ALL |
| 226R | 22 | PR | JA | | 0-0 | 31-51-12 | D00813 | | 68 | | | SM00061 | | | W | ALL |
| 226Z | | | JA | | 0-0 | 31-51-12 | D00813 | | DED | | | SM00030 | REF | | ME | ALL |
| 230 | 20 | UA | | | 4-0 | 31-51-33 | D04347J | | | JE | | GDX0003 | S.. | 2 | | ALL |
| 230B | 24 | PW | JE | | 3-0 | 31-51-33 | D04347J | | 18 | | | SM00004 | | | W | ALL |
| 230R | 24 | PW | JE | | 0-0 | 31-51-33 | D04347J | | 17 | | | SM00003 | | | W | ALL |
| 230Z | | | JE | | 0-0 | 31-51-33 | D04347J | | | JE | | SM00003 | REF | | IA | ALL |
| 236 | 20 | UA | | | 3-0 | 27-32-11 | D04347J | | | JK | | GDX0001 | S.. | 2 | | ALL |
| 236B | 24 | PW | JK | | 3-0 | 27-32-11 | D04347J | | 37 | | | D00823 | | 54 | | ALL |
| 236R | 24 | PW | JK | | 0-0 | 27-32-11 | D04347J | | 36 | | | D00823 | | 23 | | ALL |
| 236Z | | | JK | | 0-0 | 27-32-11 | D04347J | | | JK | | D00823 | DED | | | ALL |
| 237B | 24 | PW | JL | | 3-0 | 27-32-11 | D04347J | | 40 | | | D00823 | | 13 | | ALL |
| 237R | 24 | PW | JL | | 0-0 | 27-32-11 | D04347J | | 39 | | | D00823 | | 12 | | ALL |
| 237Z | | | JL | | 0-0 | 27-32-11 | D04347J | | | JK | | D00823 | DED | | | ALL |
| 238 | 20 | UA | | | 3-0 | 27-32-21 | D04349J | | | JD | | GDX0001 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 27

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|---------|-------|------|------|-----------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | |
| 238B | 24 | PW | JM | | 3-0 | 27-32-21 | D04349J | 49 | | | D01381 | 54 | | | ALL |
| 238R | 24 | PW | JM | | 0-0 | 27-32-21 | D04349J | 48 | | | D01381 | 23 | | | ALL |
| 238Z | | | JM | | 0-0 | 27-32-21 | D04349J | | | JD | D01381 | DED | | | ALL |
| 239B | 24 | PW | JN | | 3-0 | 27-32-21 | D01381 | 20 | | | D04349J | 55 | | | ALL |
| 239R | 24 | PW | JN | | 0-0 | 27-32-21 | D01381 | 19 | | | D04349J | 54 | | | ALL |
| 239Z | | | JN | | 0-0 | 27-32-21 | D01381 | DED | | | D04349J | | | JD | ALL |
| 240B | 24 | PL | JO | | 3-0 | 31-51-31 | D04347J | 23 | | | SM00080 | | W | | ALL |
| 240R | 24 | PL | JO | | 0-0 | 31-51-31 | D04347J | 22 | | | SM00042 | | W | | ALL |
| 241B | 24 | PL | JP | | 3-0 | 31-51-31 | D01487 | 60 | | | SM00080 | | W | | ALL |
| 241R | 24 | PL | JP | | 0-0 | 31-51-31 | D01487 | 28 | | | SM00042 | | W | | ALL |
| 242B | 24 | PL | JQ | | 3-0 | 31-51-32 | D00817 | 60 | | | SM00080 | | W | | ALL |
| 242R | 24 | PL | JQ | | 0-0 | 31-51-32 | D00817 | 28 | | | SM00042 | | W | | ALL |
| 243B | 24 | PW | JR | | 3-0 | 27-32-21 | D04349J | 52 | | | D01381 | 13 | | | ALL |
| 243R | 24 | PW | JR | | 0-0 | 27-32-21 | D04349J | 51 | | | D01381 | 12 | | | ALL |
| 243Z | | | JR | | 0-0 | 27-32-21 | D04349J | | | JD | D01381 | DED | | | ALL |
| 245B | 24 | PW | JT | | 3-0 | 27-32-11 | D00823 | 20 | | | D04347J | 48 | | | ALL |
| 245R | 24 | PW | JT | | 0-0 | 27-32-11 | D00823 | 19 | | | D04347J | 47 | | | ALL |
| 245Z | | | JT | | 0-0 | 27-32-11 | D00823 | DED | | | D04347J | | | JK | ALL |
| 247 | 20 | UA | | | 4-0 | 31-41-35 | D04349J | | | JV | GDX0006 | S.. | 2 | | ALL |
| 247B | 24 | PW | JV | | 4-0 | 31-41-35 | D02261 | 42 | | | D04349J | 57 | | | ALL |
| 247R | 24 | PW | JV | | 0-0 | 31-41-35 | D02261 | 43 | | | D04349J | 56 | | | ALL |
| 247Z | | | JV | | 0-0 | 31-41-35 | D02261 | DED | | | D04349J | | | JV | ALL |
| 248 | 20 | UA | | | 4-0 | 28-41-11 | D04349J | | | JW | GDX0006 | S.. | 2 | | ALL |
| 248B | 24 | PW | JW | | 4-0 | 28-41-11 | D02261 | 5 | | | D04349J | 60 | | | ALL |
| 248R | 24 | PW | JW | | 0-0 | 28-41-11 | D02261 | 8 | | | D04349J | 59 | | | ALL |
| 248Z | | | JW | | 0-0 | 28-41-11 | D02261 | DED | | | D04349J | | | JW | ALL |
| 249 | 20 | UA | | | 4-0 | 32-45-11 | D02261 | REF | | JX | GDX0003 | S.. | 2 | | ALL |
| 249B | 24 | PW | JX | | 4-0 | 32-45-11 | D02261 | 46 | | | D04301J | 17 | | | 050-099, 150-199 |
| 249B | 24 | PW | JX | | 4-0 | 32-45-11 | D02261 | 46 | | | D04511J | 23 | | | 275-299 |
| 249R | 24 | PW | JX | | 0-0 | 32-45-11 | D02261 | 48 | | | D04301J | 16 | | | 050-099, 150-199 |
| 249R | 24 | PW | JX | | 0-0 | 32-45-11 | D02261 | 48 | | | D04511J | 22 | | | 275-299 |
| 249Z | | | JX | | 0-0 | 32-45-11 | D02261 | REF | | JX | D04301J | 18 | | | 050-099, 150-199 |
| 249Z | | | JX | | 0-0 | 32-45-11 | D02261 | REF | | JX | D04511J | 24 | | | 275-299 |
| 271B | 24 | PL | KU | | 4-0 | 31-51-31 | D04397J | 5 | | | SM00088 | | W | | 050-099, 155-156, 162-166 |
| 271B | 24 | PL | KU | | 4-0 | 31-51-31 | D04597J | 5 | | | SM00088 | | W | | 150-154, 157, 167-199, 275-299 |
| 271R | 24 | PL | KU | | 0-0 | 31-51-31 | D04397J | 2 | | | SM00087 | | W | | 050-099, 155-156, 162-166 |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 28

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|-----------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | |
| 271R | 24 | PL | KU | 0-0 | 31-51-31 | D04597J | | 2 | | SM00087 | | W | | 150-154, 157, 167-199, 275-299 | |
| 272B | 24 | PL | KV | 4-0 | 31-51-31 | D01487 | | 63 | | SM00088 | | W | | ALL | |
| 272R | 24 | PL | KV | 0-0 | 31-51-31 | D01487 | | 62 | | SM00087 | | W | | ALL | |
| 273B | 24 | PL | KW | 4-0 | 31-51-32 | D00817 | | 63 | | SM00088 | | W | | ALL | |
| 273R | 24 | PL | KW | 0-0 | 31-51-32 | D00817 | | 62 | | SM00087 | | W | | ALL | |
| 301 | 20 | UA | | 3-0 | 31-51-11 | SM00028 | REF | | MA | GDX0005 | S.. | 2 | | ALL | |
| 301B | 22 | PS | MA | 3-0 | 31-51-11 | D00811 | | 57 | | SM00028 | | W | | ALL | |
| 301R | 22 | PS | MA | 0-0 | 31-51-11 | D00811 | | 38 | | SM00028 | | W | | ALL | |
| 301Y | 22 | PS | MA | 0-0 | 31-51-11 | D00811 | | 58 | | SM00028 | | W | | ALL | |
| 301Z | | | MA | 0-0 | 31-51-11 | D00811 | DED | | | SM00028 | REF | | MA | ALL | |
| 302B | 22 | PS | MB | 3-0 | 31-51-11 | D00811 | | 42 | | SM00029 | | W | | ALL | |
| 302R | 22 | PS | MB | 0-0 | 31-51-11 | D00811 | | 41 | | SM00029 | | W | | ALL | |
| 302Y | 22 | PS | MB | 0-0 | 31-51-11 | D00811 | | 43 | | SM00029 | | W | | ALL | |
| 302Z | | | MB | 0-0 | 31-51-11 | D00811 | DED | | | SM00028 | REF | | MA | ALL | |
| 303B | 22 | PS | MC | 3-0 | 31-51-11 | D00811 | | 8 | | SM00026 | | W | | ALL | |
| 303R | 22 | PS | MC | 0-0 | 31-51-11 | D00811 | | 7 | | SM00026 | | W | | ALL | |
| 303Y | 22 | PS | MC | 0-0 | 31-51-11 | D00811 | | 9 | | SM00026 | | W | | ALL | |
| 303Z | | | MC | 0-0 | 31-51-11 | D00811 | DED | | | SM00028 | REF | | MA | ALL | |
| 304B | 22 | PS | MD | 3-0 | 31-51-11 | D00811 | | 25 | | SM00027 | | W | | ALL | |
| 304R | 22 | PS | MD | 0-0 | 31-51-11 | D00811 | | 24 | | SM00027 | | W | | ALL | |
| 304Y | 22 | PS | MD | 0-0 | 31-51-11 | D00811 | | 37 | | SM00027 | | W | | ALL | |
| 304Z | | | MD | 0-0 | 31-51-11 | D00811 | DED | | | SM00028 | REF | | MA | ALL | |
| 305 | 20 | UA | | 2-0 | 31-51-12 | SM00030 | REF | | ME | GDX0005 | S.. | 2 | | ALL | |
| 305B | 22 | PS | ME | 4-0 | 31-51-12 | D00813 | | 8 | | SM00030 | | W | | ALL | |
| 305R | 22 | PS | ME | 0-0 | 31-51-12 | D00813 | | 7 | | SM00030 | | W | | ALL | |
| 305Y | 22 | PS | ME | 0-0 | 31-51-12 | D00813 | | 9 | | SM00030 | | W | | ALL | |
| 305Z | | | ME | 0-0 | 31-51-12 | D00813 | DED | | | SM00030 | REF | | ME | ALL | |
| 306B | 22 | PS | MF | 4-0 | 31-51-12 | D00813 | | 25 | | SM00031 | | W | | ALL | |
| 306R | 22 | PS | MF | 0-0 | 31-51-12 | D00813 | | 24 | | SM00031 | | W | | ALL | |
| 306Y | 22 | PS | MF | 0-0 | 31-51-12 | D00813 | | 37 | | SM00031 | | W | | ALL | |
| 306Z | | | MF | 0-0 | 31-51-12 | D00813 | DED | | | SM00030 | REF | | ME | ALL | |
| 307B | 22 | PS | MG | 4-0 | 31-51-12 | D00813 | | 57 | | SM00032 | | W | | ALL | |
| 307R | 22 | PS | MG | 0-0 | 31-51-12 | D00813 | | 38 | | SM00032 | | W | | ALL | |
| 307Y | 22 | PS | MG | 0-0 | 31-51-12 | D00813 | | 58 | | SM00032 | | W | | ALL | |
| 307Z | | | MG | 0-0 | 31-51-12 | D00813 | DED | | | SM00030 | REF | | ME | ALL | |
| 308B | 22 | PS | MH | 4-0 | 31-51-12 | D00813 | | 42 | | SM00033 | | W | | ALL | |
| 308R | 22 | PS | MH | 0-0 | 31-51-12 | D00813 | | 41 | | SM00033 | | W | | ALL | |
| 308Y | 22 | PS | MH | 0-0 | 31-51-12 | D00813 | | 43 | | SM00033 | | W | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W0040
Page 29
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | | | |
| 308Z | | | | MH | 0-0 | 31-51-12 | D00813 | | DED | | | | SM00030 | REF | | ME | ALL |
| 505 | 22 | | PA | | 4-0 | 21-66-11 | D02261 | | 18 | | | | D04347J | 56 | | | 050-099, 162-199 |
| 506 | 22 | | PA | | 4-0 | 21-66-11 | D02261 | | 51 | | | | D04347J | 57 | | | 050-099, 162-199 |
| 507 | 22 | | PA | | 4-0 | 21-66-11 | D02261 | | 52 | | | | D04347J | 58 | | | 050-099, 162-199 |
| 508 | 22 | | PA | | 4-0 | 21-66-41 | D02261 | | 19 | | | | D04347J | 59 | | | 050-099, 150, 152-199 |
| 509 | 22 | | PA | | 4-0 | 21-66-21 | D02261 | | 17 | | | | D04347J | 60 | | | 050-099, 162-199 |
| 512 | 24 | | PK | | 3-0 | 27-81-31 | D02261 | | 20 | | | | D04349J | 8 | | | ALL |
| 601 | 20 | | PA | | 0-10 | 31-51-11 | SM00060 | | | W | | | GDX0004 | D.. | 2 | | ALL |
| 602 | 20 | | PA | | 0-10 | 31-51-12 | SM00061 | | | W | | | GDX0005 | D.. | 2 | | ALL |
| 603 | 24 | | PV | YC | 3-0 | 31-51-12 | D04301J | | 5 | | | | M01103 | LINE | D | | ALL |
| 603Z | | | | YC | 0-0 | 31-51-12 | D04301J | | DED | | | | M01103 | | | YC | ALL |
| 604 | 24 | | PV | YD | 5-0 | 31-51-12 | D04301J | | 4 | | | | D00813 | 4 | | | ALL |
| 604Z | | | | YD | 0-0 | 31-51-12 | D04301J | | DED | | | | D00813 | | | YD | ALL |
| 605 | 24 | | PV | YE | 4-0 | 31-51-12 | D00813 | | 1 | | | | M01103 | LOAD | D | | ALL |
| 605Z | | | | YE | 0-0 | 31-51-12 | D00813 | | | | YD | | M01103 | DED | | | ALL |
| 606 | 24 | | PV | YF | 3-0 | 31-51-11 | D04349J | | 32 | | | | M01102 | LINE | D | | ALL |
| 606Z | | | | YF | 0-0 | 31-51-11 | D04349J | | DED | | | | M01102 | | | YF | ALL |
| 607 | 24 | | PV | YG | 5-0 | 31-51-11 | D04349J | | 33 | | | | D00811 | 4 | | | ALL |
| 607Z | | | | YG | 0-0 | 31-51-11 | D04349J | | DED | | | | D00811 | | | YG | ALL |
| 608 | 24 | | PV | YH | 5-0 | 31-51-11 | D00811 | | 1 | | | | M01102 | LOAD | D | | ALL |
| 608Z | | | | YH | 0-0 | 31-51-11 | D00811 | | | | YG | | M01102 | DED | | | ALL |
| 610 | 24 | | PK | | 3-0 | 27-32-11 | D00823 | | 37 | | | | SM00050 | | W | | ALL |
| 611 | 24 | | PK | | 3-0 | 31-51-42 | D01433 | | 6 | | | | D04347J | 20 | | | ALL |
| 612 | 24 | | PK | | 3-0 | 31-51-42 | D01433 | | 4 | | | | SM00050 | | W | | ALL |
| 613 | 24 | | PK | | 3-0 | 31-51-31 | D04349J | | 30 | | | | SM00065 | | W | | ALL |
| 614 | 24 | | PK | | 3-0 | 31-51-31 | D01487 | | 52 | | | | SM00065 | | W | | ALL |
| 615 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | 52 | | | | SM00065 | | W | | ALL |
| 617 | 24 | | PK | | 2-0 | 27-32-12 | D01381 | | 11 | | | | D00823 | 56 | | | ALL |
| 618 | 24 | | PK | | 2-0 | 27-32-12 | D01381 | | 56 | | | | D00823 | 11 | | | ALL |
| 619 | 24 | | PK | | 2-0 | 27-32-12 | D00823 | | 45 | | | | SM00082 | | W | | ALL |
| 620 | 24 | | PK | | 3-0 | 31-51-21 | D04349J | | 29 | | | | SM00071 | | W | | ALL |
| 621 | 24 | | PK | | 3-0 | 31-51-21 | D00815 | | 7 | | | | SM00071 | | W | | ALL |
| 622 | 24 | | PK | | 3-0 | 31-51-33 | D01489 | | 2 | | | | SM00071 | | W | | ALL |
| 623 | 24 | | PK | | 3-0 | 31-51-33 | D01489 | | 36 | | | | SM00038 | | W | | ALL |
| 624 | 24 | | PK | | 3-0 | 31-51-21 | D00815 | | 8 | | | | SM00045 | | W | | ALL |
| 625 | 24 | | PK | | 3-0 | 31-51-31 | D01487 | | 9 | | | | SM00034 | | W | | ALL |
| 628 | 22 | | PA | | 4-0 | 31-51-31 | D01487 | | 20 | | | | GDX0006 | D.. | 2 | | ALL |
| 629 | 22 | | PA | | 4-0 | 31-51-31 | D01487 | | 53 | | | | GDX0006 | D.. | 2 | | ALL |
| 630 | 22 | | PA | | 4-0 | 31-51-31 | D01487 | | 21 | | | | GDX0006 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 30

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | |
| 631 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | | | SM00034 | | W | | ALL |
| 634 | 22 | | PA | | 4-0 | 31-51-32 | D00817 | | | | GDX0006 | D.. | 2 | | ALL |
| 635 | 22 | | PA | | 4-0 | 31-51-32 | D00817 | | | | GDX0006 | D.. | 2 | | ALL |
| 636 | 22 | | PA | | 4-0 | 31-51-32 | D00817 | | | | GDX0006 | D.. | 2 | | ALL |
| 644 | 22 | | PQ | ZS | 3-0 | 27-32-31 | D00823 | | | | D04347J | | 42 | | ALL |
| 644Z | | | | ZS | 0-0 | 27-32-31 | D00823 | | DED | | D04347J | | DED | | ALL |
| 646 | 22 | | PQ | ZU | 3-0 | 27-32-31 | D01381 | | | | D04349J | | 42 | | ALL |
| 646Z | | | | ZU | 0-0 | 27-32-31 | D01381 | | DED | | D04349J | | DED | | ALL |
| 648 | 24 | | PK | | 4-0 | 34-16-11 | D04347J | | | | D00821 | | 40 | | 275-299 |
| 649 | 24 | | PK | | 3-0 | 34-16-11 | D04347J | | | | SM00038 | | W | | 275-299 |
| 681 | 24 | | PK | | 3-0 | 31-51-43 | D01433 | | | | D04507J | | 10 | | ALL |
| 682 | 24 | | PK | | 3-0 | 31-51-43 | D01433 | | | | D04347J | | 46 | | ALL |
| 683 | 22 | | PA | | 2-0 | 31-51-43 | D01433 | | | | SM00081 | | W | | ALL |
| 684 | 20 | | PA | | 3-0 | 31-51-43 | GDX0001 | D.. | 2 | | D04349J | | 47 | | ALL |
| 685 | 24 | | PK | | 3-0 | 27-32-12 | D00823 | | | | D01505 | | A1 | | ALL |
| 686 | 24 | | PK | | 2-0 | 27-32-11 | D00823 | | | | SM00038 | | W | | ALL |
| 687 | 24 | | PK | | 2-0 | 27-32-11 | D00823 | | | | SM00081 | | W | | ALL |
| 688 | 24 | | PK | | 3-0 | 27-32-22 | D01381 | | | | D01503 | | A1 | | ALL |
| 689 | 24 | | PK | | 2-0 | 27-32-22 | D01381 | | | | SM00085 | | W | | ALL |
| 692 | 24 | | PK | | 2-0 | 27-32-21 | D01381 | | | | SM00038 | | W | | ALL |
| 693 | 24 | | PK | | 4-0 | 31-51-21 | D04347J | | | | D00815 | | 6 | | ALL |
| 694 | 22 | | PA | | 3-0 | 31-51-43 | D04349J | | | | SM00081 | | W | | ALL |
| 696 | 20 | | PA | | 2-0 | 27-32-12 | GDX0003 | D.. | 2 | | SM00082 | | W | | ALL |
| 697 | 20 | | PA | | 2-0 | 27-32-22 | GDX0003 | D.. | 2 | | SM00085 | | W | | ALL |
| 701 | 24 | | PK | | 1-0 | 31-51-21 | D00815 | | | | D00815 | | 22 | | ALL |
| 702 | 24 | | PK | | 1-0 | 31-51-21 | D00815 | | | | D00815 | | 48 | | ALL |
| 703 | 24 | | PK | | 3-0 | 31-51-41 | D00819 | | | | SM00019 | | W | | ALL |
| 704 | 24 | | PK | | 4-0 | 31-51-41 | SM00075 | | W | | D04511J | | 14 | | ALL |
| 705 | 24 | | PK | | 4-0 | 31-51-41 | D00819 | | | | D04511J | | 12 | | ALL |
| 706 | 24 | | PK | | 4-0 | 31-51-41 | D00819 | | | | D04349J | | 31 | | ALL |
| 707 | 24 | | PK | | 4-0 | 31-51-41 | D00819 | | | | D04509J | | 4 | | ALL |
| 708 | 24 | | PK | | 4-0 | 31-51-41 | D00819 | | | | D04349J | | 7 | | ALL |
| 709 | 24 | | PK | | 3-0 | 31-51-41 | D00819 | | | | SM00044 | | W | | ALL |
| 710 | 24 | | PK | | 3-0 | 31-51-41 | D00819 | | | | SM00037 | | W | | ALL |
| 711 | 24 | | PK | | 4-0 | 31-51-41 | D00819 | | | | D04349J | | 21 | | ALL |
| 712 | 24 | | PK | | 4-0 | 31-51-41 | D00819 | | | | D04349J | | 3 | | ALL |
| 713 | 24 | | PK | | 4-0 | 31-51-41 | D00819 | | | | D04347J | | 9 | | ALL |
| 714 | 24 | | PK | | 4-0 | 31-51-41 | D00819 | | | | D04349J | | 24 | | ALL |
| 715 | 24 | | PK | | 3-0 | 31-51-42 | D04507J | | | | SM00019 | | W | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0040
Page 31
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | | | |
| 716 | 24 | | PK | 2-0 | 31-51-42 | D01433 | | 34 | | | | | SM00019 | | W | | ALL |
| 717 | 24 | | PK | 2-0 | 31-51-42 | D01433 | | 37 | | | | | SM00034 | | W | | ALL |
| 718 | 24 | | PK | 3-0 | 31-51-42 | D01433 | | 39 | | | | | D04509J | 2 | | | ALL |
| 720 | 24 | | PK | 2-0 | 31-51-42 | D01433 | | 52 | | | | | SM00040 | | W | | ALL |
| 721 | 24 | | PK | 4-0 | 31-51-42 | D01433 | | 38 | | | | | D04347J | 24 | | | ALL |
| 722 | 24 | | PK | 4-0 | 31-51-42 | D01433 | | 5 | | | | | D04349J | 22 | | | ALL |
| 723 | 24 | | PK | 3-0 | 31-51-42 | D04511J | | 11 | | | | | SM00038 | | W | | ALL |
| 724 | 24 | | PK | 2-0 | 31-51-42 | D01433 | | 40 | | | | | SM00038 | | W | | ALL |
| 725 | 24 | | PK | 4-0 | 31-51-42 | D01433 | | 3 | | | | | D04347J | 13 | | | ALL |
| 726 | 22 | | PA | 3-0 | 31-51-21 | D04347J | | 14 | | | | | SM00036 | | W | | ALL |
| 727 | 22 | | PA | 3-0 | 31-51-21 | D04301J | | 11 | | | | | SM00035 | | W | | ALL |
| 728 | 24 | | PK | 4-0 | 31-51-41 | D04347J | | 1 | | | | | D00819 | 35 | | | ALL |
| 729 | 24 | | PK | 4-0 | 31-51-41 | D04347J | | 2 | | | | | D00819 | 1 | | | ALL |
| 730 | 24 | | PK | 4-0 | 31-51-41 | D04347J | | 3 | | | | | D00819 | 36 | | | ALL |
| 731 | 24 | | PK | 4-0 | 31-51-41 | D04347J | | 4 | | | | | D00819 | 2 | | | ALL |
| 732 | 24 | | PK | 4-0 | 31-51-42 | D04347J | | 5 | | | | | D01433 | 20 | | | ALL |
| 733 | 24 | | PK | 5-0 | 34-16-11 | D04347J | | 16 | | | | | D00821 | 65 | | | ALL |
| 734 | 24 | | PK | 3-0 | 31-51-31 | D04347J | | 8 | | | | | SM00046 | | W | | ALL |
| 735 | 24 | | PK | 5-0 | 34-16-11 | D04507J | | 7 | | | | | D00821 | 34 | | | ALL |
| 736 | 24 | | PK | 4-0 | 34-16-11 | D04507J | | 2 | | | | | D00821 | 66 | | | ALL |
| 737 | 24 | | PK | 3-0 | 34-16-11 | SM00041 | | | W | | | | D00821 | 31 | | | ALL |
| 738 | 24 | | PK | 5-0 | 34-16-11 | D04347J | | 19 | | | | | D00821 | 7 | | | ALL |
| 739 | 24 | | PK | 4-0 | 34-16-11 | SM00075 | | | W | | | | D00821 | 6 | | | ALL |
| 740 | 24 | | PK | 3-0 | 34-16-11 | SM00038 | | | W | | | | D00821 | 40 | | | 050-099, 150-199 |
| 741 | 24 | | PK | 1-0 | 34-16-11 | D00821 | | 18 | | | | | D00821 | 22 | | | ALL |
| 742 | 24 | | PK | 1-0 | 34-16-11 | D00821 | | 50 | | | | | D00821 | 48 | | | ALL |
| 743 | 24 | | PK | 4-0 | 31-51-33 | D04349J | | 17 | | | | | D01489 | 20 | | | ALL |
| 746 | 24 | | PK | 3-0 | 31-51-31 | D04597J | | 10 | | | | | SM00043 | | W | | ALL |
| 747 | 24 | | PK | 3-0 | 31-51-31 | D01487 | | 46 | | | | | SM00043 | | W | | ALL |
| 748 | 24 | | PK | 3-0 | 31-51-31 | D04347J | | 7 | | | | | SM00045 | | W | | ALL |
| 749 | 24 | | PK | 3-0 | 31-51-31 | D01487 | | 10 | | | | | SM00045 | | W | | ALL |
| 750 | 24 | | PK | 3-0 | 31-51-31 | D01487 | | 19 | | | | | SM00046 | | W | | ALL |
| 751 | 24 | | PK | 3-0 | 31-51-31 | D01487 | | 13 | | | | | SM00040 | | W | | ALL |
| 752 | 24 | | PK | 3-0 | 31-51-31 | D01487 | | 47 | | | | | SM00044 | | W | | ALL |
| 753 | 24 | | PK | 3-0 | 31-51-31 | D01487 | | 51 | | | | | SM00041 | | W | | ALL |
| 755 | 24 | | PV | L5 | 3-0 | 31-51-31 | | 1 | | | | | SM00035 | | W | | ALL |
| 755Z | | | L5 | 0-0 | 31-51-31 | D01487 | | DED | | | | | SM00035 | DED | | | ALL |
| 756 | 24 | | PK | 3-0 | 31-51-31 | D01487 | | 50 | | | | | SM00036 | | W | | ALL |
| 757 | 24 | | PK | 3-0 | 31-51-31 | D01487 | | 49 | | | | | SM00039 | | W | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 32

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|-----|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | | |
| 758 | 24 | | PK | | 4-0 | 31-51-31 | D01487 | | | | D01489 | | | | 23 | ALL |
| 759 | 24 | | PK | | 4-0 | 31-51-31 | D01487 | | | | D01489 | | | | 47 | ALL |
| 760 | 24 | | PK | | 4-0 | 31-51-31 | D01487 | | | | D01489 | | | | 51 | ALL |
| 761 | 24 | | PK | | 4-0 | 31-51-31 | D01487 | | | | D01489 | | | | 57 | ALL |
| 762 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | | | SM00045 | | | | W | ALL |
| 763 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | | | SM00043 | | | | W | ALL |
| 764 | 24 | | PV | M4 | 3-0 | 31-51-32 | D00817 | | | | SM00035 | | | | W | ALL |
| 764Z | | | | M4 | 0-0 | 31-51-32 | D00817 | DED | | | SM00035 | DED | | | | ALL |
| 765 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | | | SM00036 | | | | W | ALL |
| 766 | 24 | | PV | M6 | 3-0 | 31-51-32 | D00817 | | | | SM00053 | | | | W | ALL |
| 766Z | | | | M6 | 0-0 | 31-51-32 | D00817 | DED | | | SM00053 | DED | | | | ALL |
| 767 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | | | SM00046 | | | | W | ALL |
| 768 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | | | SM00040 | | | | W | ALL |
| 769 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | | | SM00044 | | | | W | ALL |
| 770 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | | | SM00041 | | | | W | ALL |
| 772 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | | | D01489 | | | | 54 | ALL |
| 773 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | | | D01489 | | | | 13 | ALL |
| 774 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | | | D01489 | | | | 25 | ALL |
| 775 | 24 | | PK | | 3-0 | 31-51-32 | D00817 | | | | D01489 | | | | 58 | ALL |
| 776 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | D04347J | | | | 15 | ALL |
| 777 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | D04349J | | | | 13 | ALL |
| 779 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | D04349J | | | | 40 | ALL |
| 780 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | D04349J | | | | 2 | ALL |
| 781 | 24 | | PK | | 1-0 | 31-51-33 | D01489 | | | | D01489 | | | | 48 | ALL |
| 782 | 24 | | PK | | 1-0 | 31-51-33 | D01489 | | | | D01489 | | | | 22 | ALL |
| 783 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | SM00008 | | | | W | ALL |
| 784 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | SM00011 | | | | W | ALL |
| 785 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | SM00012 | | | | W | ALL |
| 786 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | SM00010 | | | | W | ALL |
| 787 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | SM00009 | | | | W | ALL |
| 788 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | SM00034 | | | | W | ALL |
| 789 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | D04509J | | | | 11 | ALL |
| 790 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | D04509J | | | | 3 | ALL |
| 791 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | D04509J | | | | 10 | ALL |
| 792 | 24 | | PK | | 4-0 | 31-51-33 | D01489 | | | | D04509J | | | | 9 | ALL |
| 793 | 24 | | PK | | 2-0 | 31-51-41 | D00819 | | | | SM00075 | | | | W | ALL |
| 794 | 20 | | PA | | 4-0 | 31-51-32 | D04303J | | | | GDX0004 | | | | S.. 2 | ALL |
| 795 | 24 | | PK | | 1-0 | 31-51-42 | D01433 | | | | D01433 | | | | 48 | ALL |
| 796 | 24 | | PK | | 1-0 | 31-51-42 | D01433 | | | | D01433 | | | | 50 | ALL |

WIRE LIST
D280T132

91-21-11
Section W0040
Page 33
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | | |
| 797 | 24 | | PV | P7 | 3-0 | 31-51-21 | D00815 | | 41 | | SM00053 | | W | | ALL | |
| 797Z | | | | P7 | 0-0 | 31-51-21 | D00815 | | DED | | SM00053 | | DED | | ALL | |
| 798 | 24 | | PV | P8 | 3-0 | 31-51-21 | D04349J | | 9 | | SM00053 | | W | | ALL | |
| 798Z | | | | P8 | 0-0 | 31-51-21 | D04349J | | DED | | SM00053 | | DED | | ALL | |
| 817 | 24 | | PK | | 3-0 | 27-32-12 | D00823 | | 55 | | D11553 | | 6 | | ALL | |
| 818 | 24 | | PK | | 3-0 | 27-32-12 | D00823 | | 21 | | D11553 | | 4 | | ALL | |
| 819 | 24 | | PK | | 3-0 | 27-32-12 | D00823 | | 51 | | D11553 | | 3 | | ALL | |
| 820 | 24 | | PK | | 3-0 | 27-32-12 | D00823 | | 50 | | D11553 | | 2 | | ALL | |
| 821 | 24 | | PK | | 3-0 | 27-32-12 | D00823 | | 49 | | D11553 | | 7 | | ALL | |
| 822 | 24 | | PK | | 3-0 | 27-32-12 | D00823 | | 47 | | D11553 | | 8 | | ALL | |
| 823 | 24 | | PK | | 3-0 | 27-32-12 | D00823 | | 46 | | D11553 | | 9 | | ALL | |
| 824 | 24 | | PK | | 3-0 | 27-32-12 | D00823 | | 53 | | D11553 | | 5 | | ALL | |
| 825 | 24 | | PK | | 3-0 | 27-32-12 | D00823 | | 62 | | D11553 | | 24 | | ALL | |
| 826 | 24 | | PK | | 3-0 | 27-32-22 | D01381 | | 55 | | D11553 | | 16 | | ALL | |
| 827 | 24 | | PK | | 3-0 | 27-32-22 | D01381 | | 21 | | D11553 | | 14 | | ALL | |
| 828 | 24 | | PK | | 3-0 | 27-32-22 | D01381 | | 51 | | D11553 | | 13 | | ALL | |
| 829 | 24 | | PK | | 3-0 | 27-32-22 | D01381 | | 50 | | D11553 | | 12 | | ALL | |
| 830 | 24 | | PK | | 3-0 | 27-32-22 | D01381 | | 49 | | D11553 | | 17 | | ALL | |
| 831 | 24 | | PK | | 3-0 | 27-32-22 | D01381 | | 47 | | D11553 | | 18 | | ALL | |
| 832 | 24 | | PK | | 3-0 | 27-32-22 | D01381 | | 46 | | D11553 | | 19 | | ALL | |
| 833 | 24 | | PK | | 3-0 | 27-32-22 | D01381 | | 53 | | D11553 | | 15 | | ALL | |
| 834 | 24 | | PK | | 3-0 | 27-32-22 | D01381 | | 62 | | D11553 | | 34 | | ALL | |
| 835 | 24 | | PK | | 3-0 | 27-32-21 | D04349J | | 50 | | D01381 | | 64 | | ALL | |
| 836 | 20 | | PA | | 3-0 | 27-32-21 | D04349J | | 53 | | GDX0002 | | S.. | 2 | ALL | |
| 837 | 24 | | PK | | 2-0 | 27-32-12 | D00823 | | 42 | | SM00082 | | W | | 150-199, 275-299 | |
| 838 | 24 | | PK | | 2-0 | 27-32-22 | D01381 | | 42 | | SM00085 | | W | | 150-199, 275-299 | |
| 839 | 24 | | PK | | 2-0 | 27-32-12 | D00823 | | 9 | | SM00082 | | W | | 050-099 | |
| 840 | 24 | | PK | | 2-0 | 27-32-22 | D01381 | | 9 | | SM00085 | | W | | 050-099 | |
| 842 | 24 | | PK | | 2-0 | 27-32-22 | D01381 | | 6 | | SM00085 | | W | | ALL | |
| 843 | 24 | | PK | | 2-0 | 27-32-12 | D00823 | | 6 | | SM00082 | | W | | ALL | |
| 862 | 22 | | PA | | 4-0 | 31-41-35 | D02261 | | 30 | | GDX0006 | | S.. | 2 | ALL | |
| 863 | 22 | | PA | | 4-0 | 31-41-35 | D02261 | | 32 | | GDX0006 | | S.. | 2 | ALL | |
| 864 | 22 | | PA | | 4-0 | 31-41-35 | D02261 | | 33 | | GDX0006 | | S.. | 2 | ALL | |
| 865 | 22 | | PA | | 4-0 | 31-41-35 | D02261 | | 64 | | GDX0006 | | S.. | 2 | ALL | |
| 866 | 24 | | PV | W6 | 3-0 | 31-51-11 | D02261 | | 27 | | SM00018 | | W | | ALL | |
| 866Z | | | | W6 | 0-0 | 31-51-11 | D02261 | | DED | | SM00018 | | REF | | X7 | ALL |
| 867 | 24 | | PV | W7 | 3-0 | 31-51-11 | D02261 | | 28 | | SM00047 | | W | | ALL | |
| 867Z | | | | W7 | 0-0 | 31-51-11 | D02261 | | DED | | SM00047 | | REF | | X8 | ALL |
| 868 | 24 | | PV | W8 | 3-0 | 31-51-12 | D02261 | | 29 | | SM00054 | | W | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 34

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | | | |
| 868Z | | | | W8 | 0-0 | 31-51-12 | D02261 | | DED | | | | SM00054 | REF | | Y0 | ALL |
| 869 | 24 | | PK | | 3-0 | 31-51-12 | D02261 | | 34 | | | | SM00025 | | W | | ALL |
| 870 | 22 | | PA | | 4-0 | 31-51-12 | D02261 | | 56 | | | | GDX0001 | S.. | 2 | | ALL |
| 871 | 22 | | PA | | 3-0 | 31-51-12 | D02261 | | 57 | | | | GDX0003 | S.. | 2 | | ALL |
| 872 | 22 | | PA | | 3-0 | 31-51-11 | D02261 | | 59 | | | | GDX0005 | S.. | 2 | | ALL |
| 873 | 24 | | PV | X3 | 3-0 | 31-51-12 | D02261 | | 60 | | | | SM00055 | | W | | ALL |
| 873Z | | | | X3 | 0-0 | 31-51-12 | D02261 | | DED | | | | SM00055 | REF | | Y1 | ALL |
| 874 | 24 | | PV | X4 | 3-0 | 31-51-11 | D02261 | | 62 | | | | SM00049 | | W | | ALL |
| 874Z | | | | X4 | 0-0 | 31-51-11 | D02261 | | DED | | | | SM00049 | REF | | X9 | ALL |
| 875 | 24 | | PV | X5 | 3-0 | 31-51-12 | D02261 | | 63 | | | | SM00056 | | W | | ALL |
| 875Z | | | | X5 | 0-0 | 31-51-12 | D02261 | | DED | | | | SM00056 | REF | | Y2 | ALL |
| 876 | 24 | | PK | | 4-0 | 31-51-11 | D02261 | | 65 | | | | SM00022 | | W | | ALL |
| 877 | 24 | | PV | X7 | 4-0 | 31-51-11 | D00811 | | 14 | | | | SM00018 | | W | | ALL |
| 877Z | | | | X7 | 0-0 | 31-51-11 | D00811 | | DED | | | | SM00018 | REF | | X7 | ALL |
| 878 | 24 | | PV | X8 | 4-0 | 31-51-11 | D00811 | | 48 | | | | SM00047 | | W | | ALL |
| 878Z | | | | X8 | 0-0 | 31-51-11 | D00811 | | DED | | | | SM00047 | REF | | X8 | ALL |
| 879 | 24 | | PV | X9 | 4-0 | 31-51-11 | D00811 | | 23 | | | | SM00049 | | W | | ALL |
| 879Z | | | | X9 | 0-0 | 31-51-11 | D00811 | | DED | | | | SM00049 | REF | | X9 | ALL |
| 880 | 24 | | PV | Y0 | 4-0 | 31-51-12 | D00813 | | 14 | | | | SM00054 | | W | | ALL |
| 880Z | | | | Y0 | 0-0 | 31-51-12 | D00813 | | DED | | | | SM00054 | REF | | Y0 | ALL |
| 881 | 24 | | PV | Y1 | 4-0 | 31-51-12 | D00813 | | 48 | | | | SM00055 | | W | | ALL |
| 881Z | | | | Y1 | 0-0 | 31-51-12 | D00813 | | DED | | | | SM00055 | REF | | Y1 | ALL |
| 882 | 24 | | PV | Y2 | 4-0 | 31-51-12 | D00813 | | 23 | | | | SM00056 | | W | | ALL |
| 882Z | | | | Y2 | 0-0 | 31-51-12 | D00813 | | DED | | | | SM00056 | REF | | Y2 | ALL |
| 883 | 22 | | PA | | 4-0 | 38-32-11 | D02261 | | 15 | | | | D04349J | | 26 | | 050-099, 156-199, 277-299 |
| 883 | 22 | | PA | | 4-0 | 38-32-11 | D02261 | | CAP | Y | | | D04349J | | 26 | | 150-154 |
| 883 | 22 | | PA | | 4-0 | 38-32-11 | D02261 | | REF | Y | | | D04349J | | 26 | | 155 |
| 884 | 22 | | PA | | 4-0 | 38-32-11 | D01741 | | REF | Y | | | D04347J | | 27 | | 050-099 |
| 884 | 22 | | PA | | 4-0 | 38-32-11 | D02261 | | CAP | Y | | | D04347J | | 27 | | 150-154 |
| 884 | 22 | | PA | | 4-0 | 38-32-11 | D02261 | | REF | Y | | | D04347J | | 27 | | 155 |
| 884 | 22 | | PA | | 4-0 | 38-32-11 | D02261 | | 47 | | | | D04347J | | 27 | | 156-199, 277-299 |
| 885 | 24 | | PK | | 3-0 | 31-51-21 | D04303J | | 9 | | | | SM00057 | | W | | ALL |
| 886 | 24 | | PK | | 3-0 | 31-51-21 | D04507J | | 3 | | | | SM00058 | | W | | ALL |
| 887 | 24 | | PK | | 3-0 | 31-51-21 | D04507J | | 1 | | | | SM00058 | | W | | ALL |
| 888 | 24 | | PK | | 3-0 | 31-51-21 | SM00057 | | | W | | | D04349J | | 44 | | ALL |
| FRA | | | | | 0-0 | 31-51-12 | M01103 | | | | YC | | M01103 | GND | D | | ALL |
| FRB | | | | | 0-0 | 31-51-12 | D00813 | | | | YD | | D00813 | | 59 | | ALL |
| FRC | | | | | 0-0 | 31-51-11 | M01102 | | | | YF | | M01102 | GND | D | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0040
Page 35
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0045 | 286T0045 | | | P51-WARNING ELECTRONICS UNIT (continued) | | | | | | | | | | | |
| FRD | | | | 0-0 | 31-51-11 | D00811 | | | | YG | D00811 | 59 | | | ALL |
| FRG | | | | 0-0 | 31-41-35 | D04349J | | 58 | | | D04349J | | | JV | ALL |
| FRH | | | | 0-0 | 28-41-11 | D04349J | | 61 | | | D04349J | | | JW | ALL |
| PA1 | | | | 0-0 | 99-99-99 | D00815 | | 47 | | | D00815 | 63 | | | ALL |
| PA2 | | | | 0-0 | 99-99-99 | D00817 | | 8 | | | D00817 | 57 | | | ALL |
| PA3 | | | | 0-0 | 99-99-99 | D00819 | | 41 | | | D00819 | 55 | | | ALL |
| PA4 | | | | 0-0 | 99-99-99 | D00821 | | 43 | | | D00821 | 60 | | | ALL |
| PA5 | | | | 0-0 | 99-99-99 | D00823 | | 52 | | | D00823 | 65 | | | ALL |
| PA6 | | | | 0-0 | 99-99-99 | D01433 | | 44 | | | D01433 | 61 | | | ALL |
| PA7 | | | | 0-0 | 99-99-99 | D01381 | | 52 | | | D01381 | 65 | | | ALL |
| PA8 | | | | 0-0 | 99-99-99 | D01487 | | 8 | | | D01487 | 57 | | | ALL |
| PA9 | | | | 0-0 | 99-99-99 | D01489 | | 56 | | | D01489 | 65 | | | ALL |
| PB4 | | | | 0-0 | 99-99-99 | D02261 | | 54 | | | D02261 | 61 | | | ALL |
| W0046 | 286T0046 | | | P6-L2-LOAD DISTRIBUTION | | | | | | | | | | | |
| 001 | 22 | | PA | 3-4 | 25-11-11 | D05934J | | 21 | | | C00354 | A2 | D | | ALL |
| 002 | 22 | | PA | 3-5 | 25-11-11 | D05934J | | 22 | | | C00354 | B2 | D | | ALL |
| 003 | 22 | | PA | 4-0 | 25-11-11 | D05934J | | 23 | | | C00354 | C2 | D | | ALL |
| 007 | 22 | | PQ | F | 3-6 | 30-32-11 | D05934J | 15 | | | C01133 | 1 | D | | ALL |
| 007Z | | | | F | 0-0 | 30-32-11 | D05934J | DED | | | C01133 | DED | | | ALL |
| 008 | 22 | | PQ | G | 3-7 | 30-33-11 | D05934J | 17 | | | C01138 | 1 | D | | ALL |
| 008Z | | | | G | 0-0 | 30-33-11 | D05934J | DED | | | C01138 | DED | | | ALL |
| 009 | 22 | | PA | 3-8 | 30-34-11 | D05934J | | 18 | | | C01122 | 1 | D | | ALL |
| 022 | 22 | | PA | 3-3 | 30-31-11 | D05934J | | 11 | | | C01110 | 2 | D | | ALL |
| 023 | 22 | | PA | 3-4 | 30-31-11 | D05934J | | 12 | | | C01111 | 2 | D | | ALL |
| 024 | 22 | | PA | 3-5 | 30-31-13 | D05934J | | 13 | | | C01112 | 2 | D | | ALL |
| 025 | 22 | | PA | 3-6 | 30-31-13 | D05934J | | 14 | | | C01113 | 2 | D | | ALL |
| 033 | 12 | | PA | 3-9 | 21-58-14 | D05934J | | 1 | | | C00331 | A2 | D | | ALL |
| 034 | 12 | | PA | 3-9 | 21-58-14 | D05934J | | 8 | | | C00331 | B2 | D | | ALL |
| 035 | 12 | | PA | 3-9 | 21-58-14 | D05934J | | 10 | | | C00331 | C2 | D | | ALL |
| 036 | 22 | | PQ | E | 3-8 | 24-51-31 | C00875 | 1 | D | | TB0016Y | A003 | BJ | | 050-099, 155-199, 277-299 |
| 036 | 22 | | PQ | E | 3-8 | 24-51-31 | C00875 | 1 | D | | TB0016Y | A013 | BJ | | 150-154, 275-276 |
| 036Z | | | | E | 0-0 | 24-51-31 | C00875 | DED | | | TB0016Y | DED | | | ALL |
| 037 | 24 | | PK | 3-9 | 24-28-11 | C00817 | | 1 | D | | TB0016X | B008 | BJ | | ALL |
| 038 | 16 | | PA | 4-1 | 28-22-11 | D05918J | | 1 | | | C00368 | A1 | D | | ALL |
| 039 | 16 | | PA | 4-1 | 28-22-11 | D05918J | | 2 | | | C00368 | B1 | D | | ALL |
| 040 | 16 | | PA | 4-1 | 28-22-11 | D05918J | | 3 | | | C00368 | C1 | D | | ALL |
| 041 | 16 | | PA | 3-10 | 28-22-11 | D05918J | | 4 | | | C00366 | A1 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 36

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0046 | 286T0046 | | | P6-L2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | |
| 042 | 16 | | PA | | 3-10 | 28-22-11 | D05918J | | | | C00366 | B1 | D | | ALL |
| 043 | 16 | | PA | | 3-10 | 28-22-11 | D05918J | | | | C00366 | C1 | D | | ALL |
| 044 | 12 | | PA | | 4-0 | 28-22-12 | D05934J | | | | C00369 | A2 | D | | ALL |
| 045 | 12 | | PA | | 4-0 | 28-22-12 | D05934J | | | | C00369 | B2 | D | | ALL |
| 046 | 12 | | PA | | 4-0 | 28-22-12 | D05934J | | | | C00369 | C2 | D | | ALL |
| 047 | 24 | | PK | | 3-0 | 24-51-42 | D05848J | | | | TB0016F | A006 | 2 | | ALL |
| 048 | 24 | | PK | | 3-0 | 24-51-42 | D05848J | | | 10 | TB0016F | C006 | 2 | | ALL |
| 049 | 24 | | PK | | 3-0 | 24-51-42 | D05848J | | | 11 | TB0016X | A009 | BJ | | ALL |
| 401B | 24 | | PN | A | 2-7 | 24-23-11 | D05848J | | | | D00310 | 1 | | | ALL |
| 401G | 24 | | PN | A | 0-0 | 24-23-11 | D05848J | | | | D00310 | 2 | | | ALL |
| 401R | 24 | | PN | A | 0-0 | 24-23-11 | D05848J | | | | D00310 | 3 | | | ALL |
| 401Y | 24 | | PN | A | 0-0 | 24-23-11 | D05848J | | | | D00310 | 4 | | | ALL |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER | | | | | | | | | | | |
| 001 | 20 | | PQ | AA | 5-0 | 23-32-11 | SM00001 | | | | D01673 | 1 | | | 050-099, 150-199 |
| 001 | 20 | | PA | | 5-0 | 23-32-11 | SM00001 | | | | D01673 | 1 | | | 275 |
| 001 | 20 | | PA | | 6-0 | 23-32-11 | SM00001 | | | | D01673 | 1 | | | 276-299 |
| 001Z | | | | AA | 0-0 | 23-32-11 | SM00001 | REF | | FG | D01673 | DED | | | 050-099, 150-199 |
| 002 | 20 | | PA | | 5-0 | 23-32-11 | SM00002 | | | | D01673 | 2 | | | 050-099, 150-199, 275 |
| 002 | 20 | | PA | | 6-0 | 23-32-11 | SM00002 | | | | D01673 | 2 | | | 276-299 |
| 003 | 22 | | PA | | 5-0 | 23-32-12 | SM00005 | | | | D01673 | 3 | | | 050-099, 151-152 |
| 003 | 22 | | PA | | 8-0 | 23-32-12 | D01209 | | 1 | | D01673 | 3 | | | 150, 153-199 |
| 003 | 22 | | PA | | 5-0 | 23-32-11 | SM00005 | | | | D01673 | 3 | | | 275 |
| 003 | 22 | | PA | | 7-0 | 23-32-11 | SM00005 | | | | D01673 | 3 | | | 276-278 |
| 003 | 22 | | PA | | 9-0 | 23-32-11 | SM00005 | | | | D01673 | 3 | | | 280-299 |
| 004 | 20 | | PA | | 5-0 | 23-32-11 | SM00003 | | | | D01673 | 4 | | | 050-099, 150-199, 275 |
| 004 | 20 | | PA | | 6-0 | 23-32-11 | SM00003 | | | | D01673 | 4 | | | 276-278 |
| 004 | 20 | | PA | | 7-0 | 23-32-11 | SM00003 | | | | D01673 | 4 | | | 280-299 |
| 005 | 20 | | PA | | 5-0 | 23-32-11 | SM00004 | | | | D01673 | 5 | | | 050-099, 150-199, 275 |
| 005 | 20 | | PA | | 6-0 | 23-32-11 | SM00004 | | | | D01673 | 5 | | | 276-278 |
| 005 | 20 | | PA | | 7-0 | 23-32-11 | SM00004 | | | | D01673 | 5 | | | 280-299 |
| 006 | 24 | | PK | | 5-0 | 23-32-12 | SM00007 | | | | D01673 | 19 | | | 050-099, 151-152 |
| 006 | 24 | | PK | | 8-0 | 23-32-12 | D01209 | | 2 | | D01673 | 19 | | | 150, 153-199 |
| 006 | 24 | | PK | | 5-0 | 23-32-11 | SM00007 | | | | D01673 | 19 | | | 275-278 |
| 006 | 24 | | PK | | 9-0 | 23-32-11 | SM00007 | | | | D01673 | 19 | | | 280-299 |
| 007 | 24 | | PK | | 5-0 | 23-32-12 | SM00006 | | | | D01673 | 20 | | | 050-099, 151-152 |
| 007 | 24 | | PK | | 8-0 | 23-32-12 | D01209 | | 3 | | D01673 | 20 | | | 150, 153-199 |
| 008 | 24 | | PV | AH | 8-0 | 23-32-12 | D01209 | | | | D01673 | 8 | | | 050-099, 150-199 |
| 008Z | | | | AH | 0-0 | 23-32-12 | D01209 | | | | D01673 | 9 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 37

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|-------|------|--------|-------|------|---------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | | |
| 010 | 24 | PV | AJ | 8-0 | 23-32-12 | D01209 | | 7 | | | | | D01673 | 10 | | 050-099, 150-199 |
| 010Z | | | AJ | 0-0 | 23-32-12 | D01209 | | 8 | | | | | D01673 | 11 | | 050-099, 150-199 |
| 011 | 20 | PQ | AK | 8-0 | 23-32-11 | SM00001 | | | S | | | | D01651 | 1 | | 050-099, 150-199 |
| 011 | 20 | PA | | 7-0 | 23-32-11 | SM00001 | | | S | | | | D01651 | 1 | | 275 |
| 011 | 20 | PA | | 6-0 | 23-32-11 | SM00001 | | | S | | | | D01651 | 1 | | 276-278 |
| 011 | 20 | PA | | 8-0 | 23-32-11 | SM00001 | | | S | | | | D01651 | 1 | | 280-299 |
| 011Z | | | AK | 0-0 | 23-32-11 | SM00001 | | REF | | FG | | | D01651 | DED | | 050-099, 150-199 |
| 012 | 20 | PA | | 8-0 | 23-32-11 | SM00002 | | | S | | | | D01651 | 2 | | 050-099, 150-199, 280-299 |
| 012 | 20 | PA | | 7-0 | 23-32-11 | SM00002 | | | S | | | | D01651 | 2 | | 275 |
| 012 | 20 | PA | | 6-0 | 23-32-11 | SM00002 | | | S | | | | D01651 | 2 | | 276-278 |
| 013 | 22 | PA | | 10-0 | 23-32-12 | D01209 | | 14 | | | | | D01651 | 3 | | 050-099, 150-199 |
| 013 | 22 | PA | | 6-0 | 23-32-11 | SM00005 | | | S | | | | D01651 | 3 | | 275 |
| 013 | 22 | PA | | 5-0 | 23-32-11 | SM00005 | | | S | | | | D01651 | 3 | | 276-278 |
| 013 | 22 | PA | | 11-0 | 23-32-11 | SM00005 | | | S | | | | D01651 | 3 | | 280-299 |
| 014 | 20 | PA | | 8-0 | 23-32-11 | SM00003 | | | S | | | | D01651 | 4 | | 050-099, 150-199 |
| 014 | 20 | PA | | 7-0 | 23-32-11 | SM00003 | | | S | | | | D01651 | 4 | | 275 |
| 014 | 20 | PA | | 6-0 | 23-32-11 | SM00003 | | | S | | | | D01651 | 4 | | 276-278 |
| 014 | 20 | PA | | 9-0 | 23-32-11 | SM00003 | | | S | | | | D01651 | 4 | | 280-299 |
| 015 | 20 | PA | | 8-0 | 23-32-11 | SM00004 | | | S | | | | D01651 | 5 | | 050-099, 150-199 |
| 015 | 20 | PA | | 6-0 | 23-32-11 | SM00004 | | | S | | | | D01651 | 5 | | 275-278 |
| 015 | 20 | PA | | 9-0 | 23-32-11 | SM00004 | | | S | | | | D01651 | 5 | | 280-299 |
| 016 | 24 | PK | | 10-0 | 23-32-12 | D01209 | | 20 | | | | | D01651 | 19 | | 050-099, 150-199 |
| 016 | 24 | PK | | 7-0 | 23-32-11 | SM00007 | | | S | | | | D01651 | 19 | | 275 |
| 016 | 24 | PK | | 6-0 | 23-32-11 | SM00007 | | | S | | | | D01651 | 19 | | 276-278 |
| 016 | 24 | PK | | 11-0 | 23-32-11 | SM00007 | | | S | | | | D01651 | 19 | | 280-299 |
| 017 | 24 | PK | | 10-0 | 23-32-12 | D01209 | | 21 | | | | | D01651 | 20 | | 050-099, 150-199 |
| 018 | 24 | PV | AR | 10-0 | 23-32-12 | D01209 | | 12 | | | | | D01651 | 8 | | 050-099, 150-199 |
| 018Z | | | AR | 0-0 | 23-32-12 | D01209 | | 13 | | | | | D01651 | 9 | | 050-099, 150-199 |
| 01CO | | | A | 0-0 | 23-32-13 | D01209 | | = C15 | | | | | D01675 | = C1 | | 050-099, 150-199 |
| 01CO | | | A | 0-0 | 23-32-13 | D01927 | | = C1 | | | | | D01675 | = C1 | | 275-299 |
| 01CX | | 5X | A | 8-0 | 23-32-13 | D01209 | | 15 | | | | | D01675 | = A1 | | 050-099, 150-199 |
| 01CX | | 5X | A | 7-4 | 23-32-13 | D01927 | | 1 | | | | | D01675 | = A1 | | 275 |
| 01CX | | 5X | A | 11-0 | 23-32-13 | D01927 | | 1 | | | | | D01675 | = A1 | | 276-278 |
| 01CX | | 5X | A | 9-0 | 23-32-13 | D01927 | | 1 | | | | | D01675 | = A1 | | 280-299 |
| 020 | 24 | PV | AT | 10-0 | 23-32-12 | D01209 | | 16 | | | | | D01651 | 10 | | 050-099, 150-199 |
| 020Z | | | AT | 0-0 | 23-32-12 | D01209 | | 17 | | | | | D01651 | 11 | | 050-099, 150-199 |
| 021 | 20 | PQ | AU | 3-0 | 23-32-11 | D06045J | | 1 | | | | | SM00001 | S | | 050-099, 150-199 |
| 021 | 20 | PA | | 3-0 | 23-32-11 | D06668P | | 26 | | | | | SM00001 | S | | 275 |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 38

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|-------|------|--------|---------|-------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | | |
| 021 | 20 | | PA | | 8-0 | 23-32-11 | D06668P | | | | SM00001 | | S | | 276-278 | |
| 021 | 20 | | PA | | 7-0 | 23-32-11 | D06668P | | | | SM00001 | | S | | 280-299 | |
| 021Z | | | | AU | 0-0 | 23-32-11 | D06045J | | | | SM00001 | REF | | FG | 050-099, 150-199 | |
| 022 | 20 | | PA | | 3-0 | 23-32-11 | D06045J | | | 2 | SM00002 | | S | | 050-099, 150-199 | |
| 022 | 20 | | PA | | 3-0 | 23-32-11 | D06668P | | | 42 | SM00002 | | S | | 275 | |
| 022 | 20 | | PA | | 8-0 | 23-32-11 | D06668P | | | 42 | SM00002 | | S | | 276-278 | |
| 022 | 20 | | PA | | 7-0 | 23-32-11 | D06668P | | | 42 | SM00002 | | S | | 280-299 | |
| 023 | 20 | | PA | | 3-0 | 23-32-11 | D06045J | | | 3 | SM00003 | | S | | 050-099, 150-199 | |
| 023 | 20 | | PA | | 3-0 | 23-32-11 | D06666P | | | 5 | SM00003 | | S | | 275 | |
| 023 | 20 | | PA | | 8-0 | 23-32-11 | D06666P | | | 5 | SM00003 | | S | | 276-278 | |
| 023 | 20 | | PA | | 6-0 | 23-32-11 | D06666P | | | 5 | SM00003 | | S | | 280-299 | |
| 024 | 20 | | PA | | 3-0 | 23-32-11 | D06045J | | | 4 | SM00004 | | S | | 050-099, 150-199 | |
| 024 | 20 | | PA | | 4-0 | 23-32-11 | D06668P | | | 38 | SM00004 | | S | | 275 | |
| 024 | 20 | | PA | | 8-0 | 23-32-11 | D06668P | | | 38 | SM00004 | | S | | 276-278 | |
| 024 | 20 | | PA | | 6-0 | 23-32-11 | D06668P | | | 38 | SM00004 | | S | | 280-299 | |
| 02CO | | | | B | 0-0 | 23-32-13 | D01209 | = C19 | | | D01653 | = C1 | | | 050-099, 150-199 | |
| 02CO | | | | B | 0-0 | 23-32-13 | D01927 | = C2 | | | D01653 | = C1 | | | 275-299 | |
| 02CX | | 5X | | B | 10-0 | 23-32-13 | D01209 | | | 19 | D01653 | = A1 | | | 050-099, 150-199 | |
| 02CX | | 5X | | B | 8-8 | 23-32-13 | D01927 | | | 2 | D01653 | = A1 | | | 275 | |
| 02CX | | 5X | | B | 11-0 | 23-32-13 | D01927 | | | 2 | D01653 | = A1 | | | 276-299 | |
| 034 | 24 | | PK | | 3-0 | 23-32-12 | D01697 | | | 7 | SM00007 | | S | | 151-152 | |
| 035 | 24 | | PK | | 3-0 | 23-32-12 | D01697 | | | 8 | SM00006 | | S | | 151-152 | |
| 036 | 22 | | PA | | 4-0 | 23-32-12 | D01697 | | | 6 | SM00005 | | S | | 151-152 | |
| 037 | 24 | | PV | BL | 4-0 | 23-32-12 | D01697 | | | 17 | D01209 | 24 | | | 151-152 | |
| 037Z | | | | BL | 0-0 | 23-32-12 | D01697 | | | 18 | D01209 | 25 | | | 151-152 | |
| 038 | 20 | | PQ | BM | 4-0 | 23-32-11 | D01697 | | | 12 | SM00001 | | S | | 050-099, 150-199 | |
| 038Z | | | | BM | 0-0 | 23-32-11 | D01697 | DED | | | SM00001 | REF | | FG | 050-099, 150-199 | |
| 039 | 20 | | PA | | 4-0 | 23-32-11 | D01697 | | | 13 | SM00002 | | S | | 050-099, 150-199 | |
| 040 | 20 | | PA | | 4-0 | 23-32-11 | D01697 | | | 4 | SM00003 | | S | | 050-099, 150-199 | |
| 041 | 20 | | PA | | 4-0 | 23-32-11 | D01697 | | | 5 | SM00004 | | S | | 050-099, 150-199 | |
| 042 | 22 | | PA | | 5-0 | 23-32-12 | D01209 | | | 1 | SM00005 | | S | | 050-099, 151-152 | |
| 043 | 24 | | PK | | 5-0 | 23-32-12 | D01209 | | | 3 | SM00006 | | S | | 050-099, 151-152 | |
| 044 | 24 | | PK | | 5-0 | 23-32-12 | D01209 | | | 2 | SM00007 | | S | | 050-099, 151-152 | |
| 04CO | | | | D | 0-0 | 23-32-13 | D06045J | = C19 | | | D01207 | = C19 | | | 050-099, 150-199 | |
| 04CX | | 5X | | D | 7-0 | 23-32-13 | D06045J | | | 19 | D01207 | 19 | | | 050-099, 150-199 | |
| 051 | 24 | | PV | CA | 7-0 | 23-32-12 | D06047J | | | 9 | D01205 | 1 | | | 050-099, 150-199 | |
| 051Z | | | | CA | 0-0 | 23-32-12 | D06047J | | | | D01205 | | | FB | 050-099, 150-199 | |
| 052 | 24 | | PV | CB | 7-0 | 23-32-12 | D06047J | | | 10 | D01205 | 2 | | | 050-099, 150-199 | |
| 052Z | | | | CB | 0-0 | 23-32-12 | D06047J | | | | D01205 | | | FB | 050-099, 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 39

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|----------|---------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | |
| 054 | 24 | PV | CD | 7-0 | 23-32-12 | D06047J | | 11 | | | D01205 | 4 | | | 050-099, 150-199 |
| 054Z | | | CD | 0-0 | 23-32-12 | D06047J | | | | FA | D01205 | | | FB | 050-099, 150-199 |
| 055 | 24 | PV | CE | 7-0 | 23-32-12 | D06047J | | 12 | | | D01205 | 5 | | | 050-099, 150-199 |
| 055Z | | | CE | 0-0 | 23-32-12 | D06047J | | | | FA | D01205 | | | FB | 050-099, 150-199 |
| 056 | 24 | PV | CF | 7-0 | 23-32-12 | D06047J | | 13 | | | D01205 | 6 | | | 050-099, 150-199 |
| 056Z | | | CF | 0-0 | 23-32-12 | D06047J | | | | FA | D01205 | | | FB | 050-099, 150-199 |
| 057 | 24 | PV | CG | 7-0 | 23-32-12 | D06047J | | 14 | | | D01205 | 7 | | | 050-099, 150-199 |
| 057Z | | | CG | 0-0 | 23-32-12 | D06047J | | | | FA | D01205 | | | FB | 050-099, 150-199 |
| 059 | 24 | PV | CI | 7-0 | 23-32-12 | D06047J | | 6 | | | D01205 | 9 | | | 050-099, 150-199 |
| 059Z | | | CI | 0-0 | 23-32-12 | D06047J | | 7 | | | D01205 | 10 | | | 050-099, 150-199 |
| 05CO | | | E | 0-0 | 23-32-13 | D06045J | | = C23 | | | D01207 | = C23 | | | 050-099, 150-199 |
| 05CX | | 5X | E | 7-0 | 23-32-13 | D06045J | | 23 | | | D01207 | 23 | | | 050-099, 150-199 |
| 061 | 24 | PK | | 7-0 | 23-32-12 | D06047J | | 8 | | | D01205 | 11 | | | 050-099, 150-199 |
| 064 | 24 | PK | | 3-0 | 23-32-12 | D06047J | | 4 | | | SM00010 | | S | | 050-099, 150-199 |
| 065 | 14 | PA | | 7-0 | 23-32-11 | D06047J | | 21 | FN | | D01205 | 15 | | | 050-099, 150-199 |
| 066 | 24 | PK | | 7-0 | 23-32-12 | D06047J | | 5 | | | D01205 | 16 | | | 050-099, 150-199 |
| 067 | 20 | PA | | 7-0 | 23-32-11 | D06047J | | 3 | | | D01205 | 17 | | | 050-099, 150-199 |
| 069 | 16 | PA | | 7-0 | 23-32-11 | D06047J | | 23 | | | D01205 | 19 | | | 050-099, 150-199 |
| 06CO | | | F | 0-0 | 23-32-13 | D01209 | | = C27 | | | D01697 | = C30 | | | 151-152 |
| 06CX | | 5X | F | 5-0 | 23-32-13 | D01209 | | 27 | | | D01697 | A30 | | | 151-152 |
| 071 | 20 | PA | | 7-0 | 23-32-13 | D06045J | | 8 | | | D01207 | 1 | | | 050-099, 150-199 |
| 072 | 24 | PK | | 7-0 | 23-32-13 | D06045J | | 5 | | | D01207 | 2 | | | 050-099, 150-199 |
| 073 | 24 | PK | | 7-0 | 23-32-13 | D06045J | | 6 | | | D01207 | 3 | | | 050-099, 150-199 |
| 074 | 24 | PK | | 7-0 | 23-32-13 | D06045J | | 7 | | | D01207 | 4 | | | 050-099, 150-199 |
| 075 | 20 | PA | | 7-0 | 23-32-13 | D06045J | | 12 | | | D01207 | 5 | | | 050-099, 150-199 |
| 076 | 24 | PK | | 7-0 | 23-32-13 | D06045J | | 9 | | | D01207 | 6 | | | 050-099, 150-199 |
| 077 | 24 | PK | | 7-0 | 23-32-13 | D06045J | | 10 | | | D01207 | 7 | | | 050-099, 150-199 |
| 078 | 24 | PK | | 7-0 | 23-32-13 | D06045J | | 11 | | | D01207 | 8 | | | 050-099, 150-199 |
| 079 | 20 | PA | | 7-0 | 23-32-13 | D06045J | | 17 | | | D01207 | 9 | | | 050-099, 150-199 |
| 07CO | | | G | 0-0 | 23-32-13 | D06049J | | = C1 | | | D01697 | = C29 | | | 151-152 |
| 07CO | | | G | 0-0 | 23-32-13 | D05597P | | = C1 | | | D01927 | = C5 | | | 275-299 |
| 07CX | | 66 | G | 5-0 | 23-32-13 | D06049J | | = A1 | | | D01697 | A29 | | | 151-152 |
| 07CX | | XA | G | 4-5 | 23-32-13 | D05597P | | = A1 | | | D01927 | 5 | | | 275 |
| 07CX | | XA | G | 12-0 | 23-32-13 | D05597P | | = A1 | | | D01927 | 5 | | | 276-278 |
| 07CX | | XA | G | 11-0 | 23-32-13 | D05597P | | = A1 | | | D01927 | 5 | | | 280-299 |
| 080 | 24 | PK | | 7-0 | 23-32-13 | D06045J | | 13 | | | D01207 | 10 | | | 050-099, 150-199 |
| 081 | 24 | PK | | 7-0 | 23-32-13 | D06045J | | 14 | | | D01207 | 11 | | | 050-099, 150-199 |
| 082 | 24 | PK | | 7-0 | 23-32-13 | D06045J | | 16 | | | D01207 | 12 | | | 050-099, 150-199 |
| 08CO | | | H | 0-0 | 23-32-13 | D06045J | | = C27 | | | D01207 | = C27 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 40

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | | | | |
| 08CX | | | 5X | H | 7-0 | 23-32-13 | D06045J | | 27 | | | | D01207 | | 27 | | | 050-099, 150-199 |
| 09CO | | | | I | 0-0 | 23-32-21 | D06045J | = | C15 | | | | D01205 | = | C27 | | | 050-099, 151 |
| 09CO | | | | I | 0-0 | 23-32-21 | D06099P | = | C15 | | | | D01927 | = | C7 | | | 275-299 |
| 09CX | | | 5X | I | 7-0 | 23-32-21 | D06045J | | 15 | | | | D01205 | | 27 | | | 050-099, 151 |
| 09CX | | | 5X | I | 4-5 | 23-32-21 | D06099P | | 15 | | | | D01927 | | 7 | | | 275 |
| 09CX | | | 5X | I | 12-0 | 23-32-21 | D06099P | | 15 | | | | D01927 | | 7 | | | 276-278 |
| 09CX | | | 5X | I | 11-0 | 23-32-21 | D06099P | | 15 | | | | D01927 | | 7 | | | 280-299 |
| 10CO | | | | AD | 0-0 | 23-32-21 | D09310 | PERG | | 1A | | | D01205 | = | C23 | | | 150, 153-199 |
| 10CO | | | | AD | 0-0 | 23-32-21 | D09310 | PERG | | 1A | | | D01205 | = | C23 | * | | 152 |
| 10CX | | | 74 | AD | 5-0 | 23-32-21 | D09310 | | 1 | | | | D01205 | | 23 | | | 150, 153-199 |
| 10CX | | | 74 | AD | 5-0 | 23-32-21 | D09310 | | 1 | | | | D01205 | | 23 | * | | 152 |
| 11CO | | | | AE | 0-0 | 23-32-21 | D09313 | = | C1 | | | | D06045J | = | C15 | | | 150, 152-199 |
| 11CX | | | 74 | AE | 5-0 | 23-32-21 | D09313 | | 1 | | | | D06045J | | 15 | | | 150, 152-199 |
| 25CO | | | | Y | 0-0 | 23-32-13 | D02239 | = | C1 | | | | D01205 | = | C23 | | | 151 |
| 25CO | | | | Y | 0-0 | 23-32-13 | D02239 | = | C1 | | | | D01205 | = | C23 | * | | 152 |
| 25CO | | | | Y | 0-0 | 23-32-13 | D01927 | = | C3 | | | | D02239 | = | C1 | | | 280-299 |
| 25CX | | | 5X | Y | 9-0 | 23-32-13 | D02239 | = | A1 | | | | D01205 | | 23 | | | 151 |
| 25CX | | | 5X | Y | 9-0 | 23-32-13 | D02239 | = | A1 | | | | D01205 | | 23 | * | | 152 |
| 25CX | | | 5X | Y | 11-0 | 23-32-13 | D01927 | | 3 | | | | D02239 | = | A1 | | | 280-299 |
| 286B | 24 | | PW | LK | 6-0 | 23-32-21 | D06047J | | 22 | | | | D02243 | | 24 | | | 050-099, 151 |
| 286B | 24 | | PW | LK | 6-0 | 23-32-21 | D06047J | | 22 | | | | D02243 | | 23 | | | 150, 152-199 |
| 286B | 24 | | PW | LK | 6-0 | 23-32-21 | D06099P | | 2 | | | | D02243 | | 24 | | | 275 |
| 286B | 24 | | PW | LK | 11-0 | 23-32-21 | D06099P | | 2 | | | | D02243 | | 24 | | | 276 |
| 286B | 24 | | PW | LK | 12-0 | 23-32-21 | D06099P | | 2 | | | | D02243 | | 24 | | | 277-278 |
| 286B | 24 | | PW | LK | 10-0 | 23-32-21 | D06099P | | 2 | | | | D02243 | | 24 | | | 280-299 |
| 286R | 24 | | PW | LK | 0-0 | 23-32-21 | D06047J | | 20 | | | | D02243 | | 23 | | | 050-099, 151 |
| 286R | 24 | | PW | LK | 0-0 | 23-32-21 | D06047J | | 20 | | | | D02243 | | 24 | | | 150, 152-199 |
| 286R | 24 | | PW | LK | 0-0 | 23-32-21 | D06099P | | 1 | | | | D02243 | | 23 | | | 275-299 |
| 286Z | | | | LK | 0-0 | 23-32-21 | D06047J | | | | FE | | D02243 | | | | FF | 050-099, 151 |
| 286Z | | | | LK | 0-0 | 23-32-21 | D06047J | | | | FE | | D02243 | | | | FU | 150, 152-199 |
| 286Z | | | | LK | 0-0 | 23-32-21 | D06099P | | | | FE | | D02243 | | | | FF | 275-299 |
| 287B | 24 | | PW | LL | 6-0 | 23-32-21 | D06047J | | 25 | | | | D02243 | | 26 | | | 050-099, 151 |
| 287B | 24 | | PW | LL | 6-0 | 23-32-21 | D06047J | | 25 | | | | D02243 | | 25 | | | 150, 152-199 |
| 287B | 24 | | PW | LL | 6-0 | 23-32-21 | D06099P | | 4 | | | | D02243 | | 26 | | | 275 |
| 287B | 24 | | PW | LL | 11-0 | 23-32-21 | D06099P | | 4 | | | | D02243 | | 26 | | | 276 |
| 287B | 24 | | PW | LL | 12-0 | 23-32-21 | D06099P | | 4 | | | | D02243 | | 26 | | | 277-278 |
| 287B | 24 | | PW | LL | 10-0 | 23-32-21 | D06099P | | 4 | | | | D02243 | | 26 | | | 280-299 |
| 287R | 24 | | PW | LL | 0-0 | 23-32-21 | D06047J | | 24 | | | | D02243 | | 25 | | | 050-099, 151 |
| 287R | 24 | | PW | LL | 0-0 | 23-32-21 | D06047J | | 24 | | | | D02243 | | 26 | | | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 41

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|----------|---------|---------|-------|------|------|----------|-------|------|------|--------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | |
| 287R | 24 | PW | LL | 0-0 | 23-32-21 | D06099P | | 3 | | | D02243 | 25 | | | 275-299 |
| 287Z | | | LL | 0-0 | 23-32-21 | D06047J | | | FE | | D02243 | | | FF | 050-099, 151 |
| 287Z | | | LL | 0-0 | 23-32-21 | D06047J | | | FE | | D02243 | | | FU | 150, 152-199 |
| 287Z | | | LL | 0-0 | 23-32-21 | D06099P | | | FE | | D02243 | | | FF | 275-299 |
| 288B | 24 | PW | LM | 6-0 | 23-32-21 | D06047J | | 34 | | | D02243 | 37 | | | 050-099, 151 |
| 288B | 24 | PW | LM | 6-0 | 23-32-21 | D06099P | | 12 | | | D02243 | 37 | | | 275 |
| 288B | 24 | PW | LM | 11-0 | 23-32-21 | D06099P | | 12 | | | D02243 | 37 | | | 276 |
| 288B | 24 | PW | LM | 12-0 | 23-32-21 | D06099P | | 12 | | | D02243 | 37 | | | 277-278 |
| 288B | 24 | PW | LM | 10-0 | 23-32-21 | D06099P | | 12 | | | D02243 | 37 | | | 280-299 |
| 288R | 24 | PW | LM | 0-0 | 23-32-21 | D06047J | | 33 | | | D02243 | 36 | | | 050-099, 151 |
| 288R | 24 | PW | LM | 0-0 | 23-32-21 | D06099P | | 11 | | | D02243 | 36 | | | 275-299 |
| 288Z | | | LM | 0-0 | 23-32-21 | D06047J | | | FE | | D02243 | | | FF | 050-099, 151 |
| 288Z | | | LM | 0-0 | 23-32-21 | D06099P | | | FE | | D02243 | | | FF | 275-299 |
| 289B | 24 | PW | LN | 8-0 | 23-31-11 | D06043J | | 4 | | | D02273 | 4 | | | 150-199 |
| 289R | 24 | PW | LN | 0-0 | 23-31-11 | D06043J | | 3 | | | D02273 | 3 | | | 150-199 |
| 289Z | | | LN | 0-0 | 23-31-11 | D06043J | | 5 | | | D02273 | 5 | | | 150-199 |
| 290B | 20 | PB | LO | 9-0 | 23-22-12 | D06043J | | 20 | | | STA00467 | CAP | Y | | 150-199 |
| 290B | 20 | PB | LO | 7-0 | 23-22-12 | D06069P | | 20 | | | STA00255 | CAP | Y | | 275 |
| 290B | 20 | PB | LO | 16-0 | 23-22-12 | D06069P | | 20 | | | STA00255 | CAP | Y | | 276-278 |
| 290R | 20 | PB | LO | 0-0 | 23-22-12 | D06043J | | 19 | | | STA00467 | CAP | Y | | 150-199 |
| 290R | 20 | PB | LO | 0-0 | 23-22-12 | D06069P | | 19 | | | STA00255 | CAP | Y | | 275-278 |
| 291B | 24 | PW | LP | 9-0 | 23-22-12 | D06043J | | 17 | | | STA00467 | CAP | Y | | 150-199 |
| 291B | 24 | PW | LP | 7-0 | 23-22-12 | D06069P | | 17 | | | STA00255 | CAP | Y | | 275 |
| 291B | 24 | PW | LP | 16-0 | 23-22-12 | D06069P | | 17 | | | STA00255 | CAP | Y | | 276-278 |
| 291R | 24 | PW | LP | 0-0 | 23-22-12 | D06043J | | 16 | | | STA00467 | CAP | Y | | 150-199 |
| 291R | 24 | PW | LP | 0-0 | 23-22-12 | D06069P | | 16 | | | STA00255 | CAP | Y | | 275-278 |
| 291Z | | | LP | 0-0 | 23-22-12 | D06043J | | 18 | | | STA00467 | DED | | | 150-199 |
| 291Z | | | LP | 0-0 | 23-22-12 | D06069P | | 18 | | | STA00255 | DED | | | 275-278 |
| 292B | 24 | PW | LQ | 9-0 | 23-22-12 | D06043J | | 14 | | | STA00467 | CAP | Y | | 150-199 |
| 292B | 24 | PW | LQ | 7-0 | 23-22-12 | D06069P | | 14 | | | STA00255 | CAP | Y | | 275 |
| 292B | 24 | PW | LQ | 16-0 | 23-22-12 | D06069P | | 14 | | | STA00255 | CAP | Y | | 276-278 |
| 292R | 24 | PW | LQ | 0-0 | 23-22-12 | D06043J | | 13 | | | STA00467 | CAP | Y | | 150-199 |
| 292R | 24 | PW | LQ | 0-0 | 23-22-12 | D06069P | | 13 | | | STA00255 | CAP | Y | | 275-278 |
| 292Z | | | LQ | 0-0 | 23-22-12 | D06043J | | 15 | | | STA00467 | DED | | | 150-199 |
| 292Z | | | LQ | 0-0 | 23-22-12 | D06069P | | 15 | | | STA00255 | DED | | | 275-278 |
| 294B | 24 | PW | LS | 9-0 | 23-31-12 | D06043J | | 25 | | | D02517 | CAP | Y | | 150 |
| 294B | 24 | PW | LS | 9-0 | 23-31-12 | D06043J | | 25 | | | D02517 | J | | | 151-199 |
| 294R | 24 | PW | LS | 0-0 | 23-31-12 | D06043J | | 26 | | | D02517 | CAP | Y | | 150 |
| 294R | 24 | PW | LS | 0-0 | 23-31-12 | D06043J | | 26 | | | D02517 | H | | | 151-199 |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 42

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|--------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | |
| 294Z | | | | LS | 0-0 | 23-31-12 | D06043J | | | | D02517 | | DED | | 150-199 |
| 305B | 24 | | PX | ME | 6-0 | 23-32-21 | D06047J | | | | D02243 | | 17 | | 050-099, 151 |
| 305B | 24 | | PX | ME | 6-0 | 23-32-21 | D06099P | | | | D02243 | | 17 | | 275 |
| 305B | 24 | | PX | ME | 11-0 | 23-32-21 | D06099P | | | | D02243 | | 17 | | 276 |
| 305B | 24 | | PX | ME | 12-0 | 23-32-21 | D06099P | | | | D02243 | | 17 | | 277-278 |
| 305B | 24 | | PX | ME | 10-0 | 23-32-21 | D06099P | | | | D02243 | | 17 | | 280-299 |
| 305R | 24 | | PX | ME | 0-0 | 23-32-21 | D06047J | | | | D02243 | | 15 | | 050-099, 151 |
| 305R | 24 | | PX | ME | 0-0 | 23-32-21 | D06099P | | | | D02243 | | 15 | | 275-299 |
| 305Y | 24 | | PX | ME | 0-0 | 23-32-21 | D06047J | | | | D02243 | | 16 | | 050-099, 151 |
| 305Y | 24 | | PX | ME | 0-0 | 23-32-21 | D06099P | | | | D02243 | | 16 | | 275-299 |
| 305Z | | | | ME | 0-0 | 23-32-21 | D06047J | | | | D02243 | | | FE | 050-099, 151 |
| 305Z | | | | ME | 0-0 | 23-32-21 | D06099P | | | | D02243 | | | FE | 275-299 |
| 306B | 24 | | PX | MF | 6-0 | 23-32-21 | D06047J | | | 30 | D02243 | | 18 | | 050-099, 151 |
| 306B | 24 | | PX | MF | 6-0 | 23-32-21 | D06047J | | | 30 | D02243 | | CAP | Y | 150, 152-199 |
| 306B | 24 | | PX | MF | 6-0 | 23-32-21 | D06099P | | | 8 | D02243 | | 18 | | 275 |
| 306B | 24 | | PX | MF | 11-0 | 23-32-21 | D06099P | | | 8 | D02243 | | 18 | | 276 |
| 306B | 24 | | PX | MF | 12-0 | 23-32-21 | D06099P | | | 8 | D02243 | | 18 | | 277-278 |
| 306B | 24 | | PX | MF | 10-0 | 23-32-21 | D06099P | | | 8 | D02243 | | 18 | | 280-299 |
| 306R | 24 | | PX | MF | 0-0 | 23-32-21 | D06047J | | | 31 | D02243 | | 19 | | 050-099, 151 |
| 306R | 24 | | PX | MF | 0-0 | 23-32-21 | D06047J | | | 31 | D02243 | | CAP | Y | 150, 152-199 |
| 306R | 24 | | PX | MF | 0-0 | 23-32-21 | D06099P | | | 9 | D02243 | | 19 | | 275-299 |
| 306Y | 24 | | PX | MF | 0-0 | 23-32-21 | D06047J | | | 32 | D02243 | | 20 | | 050-099, 151 |
| 306Y | 24 | | PX | MF | 0-0 | 23-32-21 | D06047J | | | 32 | D02243 | | CAP | Y | 150, 152-199 |
| 306Y | 24 | | PX | MF | 0-0 | 23-32-21 | D06099P | | | 10 | D02243 | | 20 | | 275-299 |
| 306Z | | | | MF | 0-0 | 23-32-21 | D06047J | | | | D02243 | | | FE | 050-099, 151 |
| 306Z | | | | MF | 0-0 | 23-32-21 | D06047J | | | 26 | D02243 | | DED | | 150, 152-156, 162-199 |
| 306Z | | | | MF | 0-0 | 23-32-21 | D06047J | | | 26 | D02243 | | | | 157 |
| 306Z | | | | MF | 0-0 | 23-32-21 | D06099P | | | | D02243 | | | FE | 275-299 |
| 401B | 20 | | PD | QA | 7-0 | 23-32-13 | D06047J | | | 37 | D01207 | | 21 | | 150-199 |
| 401B | 20 | | PD | QA | 5-0 | 23-32-13 | D06668P | | | 36 | D01933 | | 29 | | 275 |
| 401B | 20 | | PD | QA | 11-0 | 23-32-13 | D06668P | | | 36 | D01933 | | 29 | | 276-299 |
| 401G | 20 | | PD | QA | 0-0 | 23-32-13 | D06047J | | | 35 | D01207 | | 20 | | 150-199 |
| 401G | 20 | | PD | QA | 0-0 | 23-32-13 | D06668P | | | 34 | D01933 | | 28 | | 275-299 |
| 401R | 20 | | PD | QA | 0-0 | 23-32-13 | D06047J | | | 38 | D01207 | | 18 | | 150-199 |
| 401R | 20 | | PD | QA | 0-0 | 23-32-13 | D06668P | | | 37 | D01933 | | 27 | | 275-299 |
| 401Y | 20 | | PD | QA | 0-0 | 23-32-13 | D06047J | | | 36 | D01207 | | 22 | | 150-199 |
| 401Y | 20 | | PD | QA | 0-0 | 23-32-13 | D06668P | | | 35 | D01933 | | 30 | | 275-299 |
| 501 | 24 | | PV | UA | 10-0 | 23-32-12 | D02241 | | | 8 | D01209 | | 9 | | 151 |
| 501 | 24 | | PV | UA | 10-0 | 23-32-12 | D02241 | | | 8 | D01209 | | 9 | | 152 |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 43

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|-------------|------|---------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | |
| 501Z | | | | UA | 0-0 | 23-32-12 | D02241 | | 9 | | | D01209 | 10 | | 151 |
| 501Z | | | | UA | 0-0 | 23-32-12 | D02241 | | 9 | | | D01209 | 10 | * | 152 |
| 502 | 24 | | PV | UB | 10-0 | 23-32-12 | D02241 | | 10 | | | D01209 | 11 | | 151 |
| 502 | 24 | | PV | UB | 10-0 | 23-32-12 | D02241 | | 10 | | | D01209 | 11 | * | 152 |
| 502Z | | | | UB | 0-0 | 23-32-12 | D02241 | | 11 | | | D01209 | 18 | | 151 |
| 502Z | | | | UB | 0-0 | 23-32-12 | D02241 | | 11 | | | D01209 | 18 | * | 152 |
| 503 | 22 | | PA | | 9-0 | 23-32-12 | D02241 | | 3 | | | D01205 | 24 | | 151-152 |
| 503 | 22 | | PA | | 11-0 | 23-32-11 | SM00005 | | | S | | D02241 | 3 | | 280-299 |
| 504 | 24 | | PK | | 7-0 | 23-32-12 | D02241 | | 6 | | | SM00010 | | S | 151-152 |
| 505 | 24 | | PK | | 9-0 | 23-32-12 | D02241 | | 20 | | | D01205 | 21 | | 151-152 |
| 506 | 24 | | PK | | 9-0 | 23-32-12 | D02241 | | 19 | | | D01205 | 20 | | 151-152 |
| 507 | 20 | | PA | | 7-0 | 23-32-12 | D02243 | | 39 | | | D01205 | 18 | | 050-099, 151 |
| 507 | 20 | | PA | | 7-0 | 23-32-12 | D02243 | | 39 | | * | D01205 | 18 | | 150, 152-199 |
| 508 | 24 | | PK | | 5-0 | 23-32-12 | SM00010 | | | S | | D01673 | 6 | | 050-099, 150-199 |
| 509 | 24 | | PK | | 7-0 | 23-32-12 | SM00010 | | | S | | D01651 | 6 | | 050-099, 150-199 |
| 510 | 20 | | PA | | 7-0 | 23-32-11 | D02241 | | 5 | | | SM00004 | | S | 050-099, 150-199 |
| 510 | 20 | | PA | | 9-0 | 23-32-11 | SM00004 | | | S | | D02241 | 5 | | 280-299 |
| 511 | 20 | | PA | | 7-0 | 23-32-11 | D02241 | | 4 | | | SM00003 | | S | 050-099, 150-199 |
| 511 | 20 | | PA | | 9-0 | 23-32-11 | SM00003 | | | S | | D02241 | 4 | | 280-299 |
| 512 | 20 | | PA | | 7-0 | 23-32-11 | D02241 | | 2 | | | SM00002 | | S | 050-099, 150-199 |
| 512 | 20 | | PA | | 6-0 | 23-32-11 | SM00002 | | | S | | D02241 | 2 | | 280-299 |
| 513 | 20 | | PQ | UM | 7-0 | 23-32-11 | D02241 | | 1 | | | SM00001 | | S | 050-099, 150-199 |
| 513 | 20 | | PA | | 6-0 | 23-32-11 | SM00001 | | | S | | D02241 | 1 | | 280-299 |
| 513Z | | | | UM | 0-0 | 23-32-11 | D02241 | | | DED | | SM00001 | REF | | FG 050-099, 150-199 |
| 514 | 20 | | PA | | 4-0 | 23-32-21 | D02243 | | 41 | | | SM00002 | | S | 050-099 |
| 514 | 20 | | PA | | 4-0 | 23-32-11 | D02243 | | 41 | | * | SM00002 | | S | 150, 152-199 |
| 514 | 20 | | PA | | 4-0 | 23-32-11 | D02243 | | 41 | | | SM00002 | | S | 151 |
| 514 | 20 | | PA | | 5-0 | 23-32-11 | D02243 | | 41 | | | SM00004 | | S | 275 |
| 514 | 20 | | PA | | 6-0 | 23-32-11 | D02243 | | 41 | | | SM00004 | | S | 276, 280-299 |
| 514 | 20 | | PA | | 7-0 | 23-32-11 | D02243 | | 41 | | | SM00004 | | S | 277-278 |
| 515 | 20 | | PA | | 4-0 | 23-32-21 | D02243 | | 40 | | | SM00003 | | S | 050-099 |
| 515 | 20 | | PA | | 4-0 | 23-32-11 | D02243 | | 40 | | * | SM00003 | | S | 150, 152-199 |
| 515 | 20 | | PA | | 4-0 | 23-32-11 | D02243 | | 40 | | | SM00003 | | S | 151, 275 |
| 515 | 20 | | PA | | 5-0 | 23-32-11 | D02243 | | 40 | | | SM00003 | | S | 276 |
| 515 | 20 | | PA | | 6-0 | 23-32-11 | D02243 | | 40 | | | SM00003 | | S | 277-299 |
| 516 | 24 | | PK | | 8-0 | 23-31-11 | D06043J | | 1 | | | D02273 | 1 | | 150-199 |
| 517 | 24 | | PK | | 8-0 | 23-31-11 | D06043J | | 2 | | | D02273 | 2 | | 150-199 |
| 518 | 24 | | PK | | 8-0 | 23-31-13 | D06043J | | 6 | | | D02273 | 12 | | 150-199 |
| 519 | 24 | | PK | | 7-0 | 23-31-13 | SM00009 | | | S | | D02273 | 8 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 44

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | | |
| 520 | 24 | | PK | | 8-0 | 23-31-13 | D06043J | | 8 | | | D02273 | | 9 | | 150-199 |
| 521 | 24 | | PK | | 8-0 | 23-31-13 | D06043J | | 9 | | | D02273 | | 10 | | 150-199 |
| 522 | 24 | | PK | | 8-0 | 23-31-13 | D06043J | | 10 | | | D02273 | | 11 | | 150-199 |
| 523 | 24 | | PK | | 8-0 | 23-31-14 | D06043J | | 11 | | | D02273 | | 7 | | 150-153, 167-199 |
| 523 | 24 | | PK | | 8-0 | 23-31-13 | D06043J | | 11 | | | D02273 | | 7 | | 154-166 |
| 524 | 24 | | PK | | 8-0 | 23-31-14 | D06043J | | 12 | | | D02273 | | 6 | | 150-153, 167-199 |
| 524 | 24 | | PK | | 8-0 | 23-31-13 | D06043J | | 12 | | | D02273 | | 6 | | 154-166 |
| 527 | 24 | | PK | | 9-0 | 23-31-12 | D02517 | CAP | Y | | | D06043J | | 24 | | 150 |
| 527 | 24 | | PK | | 9-0 | 23-31-12 | D02517 | | B | | | D06043J | | 24 | | 151-199 |
| 528 | 24 | | PK | | 9-0 | 23-31-12 | D02517 | CAP | Y | | | D06043J | | 23 | | 150 |
| 528 | 24 | | PK | | 9-0 | 23-31-12 | D02517 | | D | | | D06043J | | 23 | | 151-199 |
| 529 | 24 | | PK | | 9-0 | 23-31-12 | D02517 | CAP | Y | | | D06043J | | 21 | | 150 |
| 529 | 24 | | PK | | 9-0 | 23-31-12 | D02517 | | C | | | D06043J | | 21 | | 151-199 |
| 530 | 24 | | PK | | 3-0 | 23-31-12 | SM00009 | | | S | | D06043J | | 7 | | 150-199 |
| 531 | 24 | | PK | | 9-0 | 23-31-12 | D02517 | CAP | Y | | | D06043J | | 27 | | 150 |
| 531 | 24 | | PK | | 9-0 | 23-31-12 | D02517 | | V | | | D06043J | | 27 | | 151-199 |
| 532 | 24 | | PK | | 6-0 | 23-31-12 | SM00009 | | | S | | D02517 | CAP | Y | | 150 |
| 532 | 24 | | PK | | 6-0 | 23-31-12 | SM00009 | | | S | | D02517 | | E | | 151-199 |
| 533 | 22 | | PA | | 7-0 | 23-32-12 | D06047J | | | 18 | | D01207 | | 24 | | 050-099, 150-199 |
| 534 | 22 | | PA | | 7-0 | 23-32-12 | D06047J | | | 16 | | D01207 | | 25 | | 050-099, 150-199 |
| 535 | 22 | | PA | | 7-0 | 23-32-12 | D06047J | | | 17 | | D01207 | | 26 | | 050-099, 150-199 |
| 536 | 24 | | PV | VK | 9-0 | 23-34-14 | D06043J | | | 28 | | D02517 | CAP | Y | | 150 |
| 536 | 24 | | PV | VK | 9-0 | 23-34-14 | D06043J | | | 28 | | D02517 | | K | | 151-199 |
| 536Z | | | | VK | 0-0 | 23-34-14 | D06043J | | | 29 | | D02517 | | L | | 150-199 |
| 537 | 24 | | PV | VL | 9-0 | 23-34-14 | D06043J | | | 30 | | D02517 | CAP | Y | | 150 |
| 537 | 24 | | PV | VL | 9-0 | 23-34-14 | D06043J | | | 30 | | D02517 | | M | | 151-199 |
| 537Z | | | | VL | 0-0 | 23-34-14 | D06043J | | | 31 | | D02517 | | N | | 150-199 |
| 538 | 20 | | PQ | VM | 6-0 | 23-32-11 | D01205 | | | 12 | | SM00001 | | S | | 050-099, 150-199 |
| 538Z | | | | VM | 0-0 | 23-32-11 | D01205 | DED | | | | SM00001 | REF | | FG | 050-099, 150-199 |
| 539 | 20 | | PA | | 6-0 | 23-32-11 | D01205 | | | 13 | | SM00002 | | S | | 050-099, 150-199 |
| 544B | 24 | | PW | VS | 5-0 | 23-32-12 | D01931 | | | 19 | | D06666P | | 3 | | 275 |
| 544B | 24 | | PW | VS | 12-0 | 23-32-12 | D01931 | | | 19 | | D06666P | | 3 | | 276-278 |
| 544B | 24 | | PW | VS | 11-0 | 23-32-12 | D01931 | | | 19 | | D06666P | | 3 | | 280-299 |
| 544R | 24 | | PW | VS | 0-0 | 23-32-12 | D01931 | | | 18 | | D06666P | | 2 | | 275-299 |
| 544Z | | | | VS | 0-0 | 23-32-12 | D01931 | | | 26 | | D06666P | | 1 | | 275-299 |
| 545B | 24 | | PW | VT | 5-0 | 23-32-12 | D01931 | | | 2 | | D06666P | | 19 | | 275 |
| 545B | 24 | | PW | VT | 12-0 | 23-32-12 | D01931 | | | 2 | | D06666P | | 19 | | 276-278 |
| 545B | 24 | | PW | VT | 11-0 | 23-32-12 | D01931 | | | 2 | | D06666P | | 19 | | 280-299 |
| 545R | 24 | | PW | VT | 0-0 | 23-32-12 | D01931 | | | 1 | | D06666P | | 18 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 45

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | | |
| 545Z | | | | VT | 0-0 | 23-32-12 | D01931 | | | | FH | D06666P | | | FI | 275-299 |
| 546B | 24 | PW | VU | VU | 5-0 | 23-32-12 | D01931 | 4 | | | | D06666P | 37 | | | 275 |
| 546B | 24 | PW | VU | VU | 12-0 | 23-32-12 | D01931 | 4 | | | | D06666P | 37 | | | 276-278 |
| 546B | 24 | PW | VU | VU | 11-0 | 23-32-12 | D01931 | 4 | | | | D06666P | 37 | | | 280-299 |
| 546R | 24 | PW | VU | VU | 0-0 | 23-32-12 | D01931 | 3 | | | | D06666P | 20 | | | 275-299 |
| 546Z | | | | VU | 0-0 | 23-32-12 | D01931 | | | | FH | D06666P | | | FI | 275-299 |
| 547B | 24 | PW | VV | VV | 5-0 | 23-32-12 | D01931 | 6 | | | | D06666P | 15 | | | 275 |
| 547B | 24 | PW | VV | VV | 12-0 | 23-32-12 | D01931 | 6 | | | | D06666P | 15 | | | 276-278 |
| 547B | 24 | PW | VV | VV | 11-0 | 23-32-12 | D01931 | 6 | | | | D06666P | 15 | | | 280-299 |
| 547R | 24 | PW | VV | VV | 0-0 | 23-32-12 | D01931 | 5 | | | | D06666P | 14 | | | 275-299 |
| 547Z | | | | VV | 0-0 | 23-32-12 | D01931 | | | | FH | D06666P | | | FJ | 275-299 |
| 548B | 24 | PW | VW | VW | 5-0 | 23-32-12 | D01931 | 8 | | | | D06666P | 31 | | | 275 |
| 548B | 24 | PW | VW | VW | 12-0 | 23-32-12 | D01931 | 8 | | | | D06666P | 31 | | | 276-278 |
| 548B | 24 | PW | VW | VW | 11-0 | 23-32-12 | D01931 | 8 | | | | D06666P | 31 | | | 280-299 |
| 548R | 24 | PW | VW | VW | 0-0 | 23-32-12 | D01931 | 7 | | | | D06666P | 30 | | | 275-299 |
| 548Z | | | | VW | 0-0 | 23-32-12 | D01931 | | | | FH | D06666P | | | FJ | 275-299 |
| 549B | 24 | PW | VX | VX | 5-0 | 23-32-12 | D01931 | 10 | | | | D06666P | 33 | | | 275 |
| 549B | 24 | PW | VX | VX | 12-0 | 23-32-12 | D01931 | 10 | | | | D06666P | 33 | | | 276-278 |
| 549B | 24 | PW | VX | VX | 11-0 | 23-32-12 | D01931 | 10 | | | | D06666P | 33 | | | 280-299 |
| 549R | 24 | PW | VX | VX | 0-0 | 23-32-12 | D01931 | 9 | | | | D06666P | 17 | | | 275-299 |
| 549Z | | | | VX | 0-0 | 23-32-12 | D01931 | | | | FH | D06666P | | | FK | 275-299 |
| 550B | 24 | PW | VY | VY | 5-0 | 23-32-12 | D01931 | 12 | | | | D06666P | 35 | | | 275 |
| 550B | 24 | PW | VY | VY | 12-0 | 23-32-12 | D01931 | 12 | | | | D06666P | 35 | | | 276-278 |
| 550B | 24 | PW | VY | VY | 11-0 | 23-32-12 | D01931 | 12 | | | | D06666P | 35 | | | 280-299 |
| 550R | 24 | PW | VY | VY | 0-0 | 23-32-12 | D01931 | 11 | | | | D06666P | 34 | | | 275-299 |
| 550Z | | | | VY | 0-0 | 23-32-12 | D01931 | | | | FH | D06666P | | | FK | 275-299 |
| 551B | 24 | PW | WA | WA | 8-0 | 23-32-13 | D01931 | 28 | | | | D01673 | 9 | | | 275 |
| 551B | 24 | PW | WA | WA | 11-0 | 23-32-13 | D01931 | 28 | | | | D01673 | 9 | | | 276-278 |
| 551B | 24 | PW | WA | WA | 9-0 | 23-32-13 | D01931 | 28 | | | | D01673 | 9 | | | 280-299 |
| 551R | 24 | PW | WA | WA | 0-0 | 23-32-13 | D01931 | 27 | | | | D01673 | 8 | | | 275-299 |
| 551Z | | | | WA | 0-0 | 23-32-13 | D01931 | DED | | | | D01673 | | | FL | 275-299 |
| 552B | 24 | PW | WB | WB | 8-0 | 23-32-13 | D01931 | 30 | | | | D01673 | 11 | | | 275 |
| 552B | 24 | PW | WB | WB | 11-0 | 23-32-13 | D01931 | 30 | | | | D01673 | 11 | | | 276-278 |
| 552B | 24 | PW | WB | WB | 9-0 | 23-32-13 | D01931 | 30 | | | | D01673 | 11 | | | 280-299 |
| 552R | 24 | PW | WB | WB | 0-0 | 23-32-13 | D01931 | 29 | | | | D01673 | 10 | | | 275-299 |
| 552Z | | | | WB | 0-0 | 23-32-13 | D01931 | DED | | | | D01673 | | | FL | 275-299 |
| 553B | 24 | PW | WC | WC | 10-0 | 23-32-13 | D01931 | 32 | | | | D01651 | 9 | | | 275 |
| 553B | 24 | PW | WC | WC | 11-0 | 23-32-13 | D01931 | 32 | | | | D01651 | 9 | | | 276-299 |
| 553R | 24 | PW | WC | WC | 0-0 | 23-32-13 | D01931 | 31 | | | | D01651 | 8 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 46

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|----|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | | | |
| 553Z | | | | WC | 0-0 | 23-32-13 | D01931 | | DED | | | | D01651 | | | FM | 275-299 |
| 554B | 24 | | PW | WD | 10-0 | 23-32-13 | D01931 | | 34 | | | | D01651 | 11 | | | 275 |
| 554B | 24 | | PW | WD | 11-0 | 23-32-13 | D01931 | | 34 | | | | D01651 | 11 | | | 276-299 |
| 554R | 24 | | PW | WD | 0-0 | 23-32-13 | D01931 | | 33 | | | | D01651 | 10 | | | 275-299 |
| 554Z | | | | WD | 0-0 | 23-32-13 | D01931 | | DED | | | | D01651 | | | FM | 275-299 |
| 555B | 24 | | PW | WE | 5-0 | 23-32-31 | D01929 | | 20 | | | | D06668P | 2 | | | 275 |
| 555B | 24 | | PW | WE | 12-0 | 23-32-31 | D01929 | | 20 | | | | D06668P | 2 | | | 276-278 |
| 555B | 24 | | PW | WE | 11-0 | 23-32-31 | D01929 | | 20 | | | | D06668P | 2 | | | 280-299 |
| 555R | 24 | | PW | WE | 0-0 | 23-32-31 | D01929 | | 19 | | | | D06668P | 1 | | | 275-299 |
| 555Z | | | | WE | 0-0 | 23-32-31 | D01929 | | 21 | | | | D06668P | 3 | | | 275-299 |
| 556B | 24 | | 7P | WF | 5-0 | 23-32-31 | D01929 | | 2 | | | | D06668P | 9 | | | 275 |
| 556B | 24 | | 7P | WF | 12-0 | 23-32-31 | D01929 | | 2 | | | | D06668P | 9 | | | 276-278 |
| 556B | 24 | | 7P | WF | 11-0 | 23-32-31 | D01929 | | 2 | | | | D06668P | 9 | | | 280-299 |
| 556BN | 24 | | 7P | WF | 0-0 | 23-32-31 | D01929 | | 1 | | | | D06668P | 8 | | | 275-299 |
| 556Z | | | | WF | 0-0 | 23-32-31 | D01929 | | 3 | | | | D06668P | 10 | | | 275-299 |
| 557B | 24 | | 7P | WG | 5-0 | 23-32-31 | D01929 | | 5 | | | | D06668P | 16 | | | 275 |
| 557B | 24 | | 7P | WG | 12-0 | 23-32-31 | D01929 | | 5 | | | | D06668P | 16 | | | 276-278 |
| 557B | 24 | | 7P | WG | 11-0 | 23-32-31 | D01929 | | 5 | | | | D06668P | 16 | | | 280-299 |
| 557BN | 24 | | 7P | WG | 0-0 | 23-32-31 | D01929 | | 4 | | | | D06668P | 15 | | | 275-299 |
| 557Z | | | | WG | 0-0 | 23-32-31 | D01929 | | 6 | | | | D06668P | 17 | | | 275-299 |
| 558B | 24 | | 7P | WH | 5-0 | 23-32-31 | D01929 | | 8 | | | | D06668P | 19 | | | 275 |
| 558B | 24 | | 7P | WH | 12-0 | 23-32-31 | D01929 | | 8 | | | | D06668P | 19 | | | 276-278 |
| 558B | 24 | | 7P | WH | 11-0 | 23-32-31 | D01929 | | 8 | | | | D06668P | 19 | | | 280-299 |
| 558BN | 24 | | 7P | WH | 0-0 | 23-32-31 | D01929 | | 7 | | | | D06668P | 18 | | | 275-299 |
| 558Z | | | | WH | 0-0 | 23-32-31 | D01929 | | 9 | | | | D06668P | 20 | | | 275-299 |
| 559B | 24 | | PW | WI | 5-0 | 23-32-51 | D01929 | | 23 | | | | D06668P | 44 | | | 275 |
| 559B | 24 | | PW | WI | 12-0 | 23-32-51 | D01929 | | 23 | | | | D06668P | 44 | | | 276-278 |
| 559B | 24 | | PW | WI | 11-0 | 23-32-51 | D01929 | | 23 | | | | D06668P | 44 | | | 280-299 |
| 559R | 24 | | PW | WI | 0-0 | 23-32-51 | D01929 | | 22 | | | | D06668P | 43 | | | 275-299 |
| 559Z | | | | WI | 0-0 | 23-32-51 | D01929 | | 24 | | | | D06668P | 45 | | | 275-299 |
| 560B | 24 | | 7P | WJ | 5-0 | 23-32-51 | D01929 | | 11 | | | | D06668P | 47 | | | 275 |
| 560B | 24 | | 7P | WJ | 12-0 | 23-32-51 | D01929 | | 11 | | | | D06668P | 47 | | | 276-278 |
| 560B | 24 | | 7P | WJ | 11-0 | 23-32-51 | D01929 | | 11 | | | | D06668P | 47 | | | 280-299 |
| 560BN | 24 | | 7P | WJ | 0-0 | 23-32-51 | D01929 | | 10 | | | | D06668P | 46 | | | 275-299 |
| 560Z | | | | WJ | 0-0 | 23-32-51 | D01929 | | 12 | | | | D06668P | 48 | | | 275-299 |
| 561B | 24 | | 7P | WK | 5-0 | 23-32-51 | D01929 | | 14 | | | | D06668P | 50 | | | 275 |
| 561B | 24 | | 7P | WK | 12-0 | 23-32-51 | D01929 | | 14 | | | | D06668P | 50 | | | 276-278 |
| 561B | 24 | | 7P | WK | 11-0 | 23-32-51 | D01929 | | 14 | | | | D06668P | 50 | | | 280-299 |
| 561BN | 24 | | 7P | WK | 0-0 | 23-32-51 | D01929 | | 13 | | | | D06668P | 49 | | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0040
Page 47
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | | | |
| 561Z | | | | WK | 0-0 | 23-32-51 | D01929 | | 15 | | | | D06668P | 51 | | | 275-299 |
| 562B | 24 | | 7P | WL | 5-0 | 23-32-51 | D01929 | | 17 | | | | D06668P | 53 | | | 275 |
| 562B | 24 | | 7P | WL | 12-0 | 23-32-51 | D01929 | | 17 | | | | D06668P | 53 | | | 276-278 |
| 562B | 24 | | 7P | WL | 11-0 | 23-32-51 | D01929 | | 17 | | | | D06668P | 53 | | | 280-299 |
| 562BN | 24 | | 7P | WL | 0-0 | 23-32-51 | D01929 | | 16 | | | | D06668P | 52 | | | 275-299 |
| 562Z | | | | WL | 0-0 | 23-32-51 | D01929 | | 18 | | | | D06668P | 54 | | | 275-299 |
| 563 | 20 | | PA | | 5-0 | 23-32-11 | D02243 | | 39 | | | | SM00005 | | S | | 275 |
| 563 | 20 | | PA | | 6-0 | 23-32-11 | D02243 | | 39 | | | | SM00005 | | S | | 276 |
| 563 | 20 | | PA | | 12-0 | 23-32-11 | D02243 | | 39 | | | | SM00013 | | S | | 277-278 |
| 563 | 20 | | PA | | 10-0 | 23-32-11 | D02243 | | 39 | | | | SM00013 | | S | | 280-299 |
| 570 | 20 | | PA | | 5-0 | 23-32-11 | D01933 | | 3 | | | | D06666P | 4 | | | 275 |
| 570 | 20 | | PA | | 12-0 | 23-32-11 | D01933 | | 3 | | | | D06666P | 4 | | | 276 |
| 570 | 20 | | PA | | 1-0 | 23-32-11 | D06666P | | 4 | | | | SM00013 | | S | | 277-299 |
| 571 | 20 | | PA | | 4-0 | 23-32-11 | D01933 | | 4 | | | | SM00003 | | S | | 275 |
| 571 | 20 | | PA | | 5-0 | 23-32-11 | D01933 | | 4 | | | | SM00003 | | S | | 276-278 |
| 571 | 20 | | PA | | 7-0 | 23-32-11 | D01933 | | 4 | | | | SM00003 | | S | | 280-299 |
| 572 | 20 | | PA | | 5-0 | 23-32-11 | D01933 | | 5 | | | | SM00004 | | S | | 275 |
| 572 | 20 | | PA | | 6-0 | 23-32-11 | D01933 | | 5 | | | | SM00004 | | S | | 276-278 |
| 572 | 20 | | PA | | 7-0 | 23-32-11 | D01933 | | 5 | | | | SM00004 | | S | | 280-299 |
| 573 | 20 | | PA | | 4-0 | 23-32-11 | D01933 | | 2 | | | | SM00002 | | S | | 275 |
| 573 | 20 | | PA | | 5-0 | 23-32-11 | D01933 | | 2 | | | | SM00002 | | S | | 276-278 |
| 573 | 20 | | PA | | 6-0 | 23-32-11 | D01933 | | 2 | | | | SM00002 | | S | | 280-299 |
| 574 | 20 | | PA | | 4-0 | 23-32-11 | D01933 | | 1 | | | | SM00001 | | S | | 275 |
| 574 | 20 | | PA | | 5-0 | 23-32-11 | D01933 | | 1 | | | | SM00001 | | S | | 276-278 |
| 574 | 20 | | PA | | 6-0 | 23-32-11 | D01933 | | 1 | | | | SM00001 | | S | | 280-299 |
| 575 | 20 | | PA | | 5-0 | 23-32-11 | D01933 | | 24 | | | | SM00005 | | S | | 275 |
| 575 | 20 | | PA | | 7-0 | 23-32-11 | D01933 | | 24 | | | | SM00005 | | S | | 276-278 |
| 575 | 20 | | PA | | 1-0 | 23-32-11 | D01933 | | 24 | | | | SM00005 | | S | | 280-299 |
| 576 | 22 | | PA | | 4-0 | 23-32-11 | D01933 | | 25 | | | | SM00007 | | S | | 275 |
| 576 | 22 | | PA | | 6-0 | 23-32-11 | D01933 | | 25 | | | | SM00007 | | S | | 276-278 |
| 576 | 22 | | PA | | 1-0 | 23-32-11 | D01933 | | 25 | | | | SM00007 | | S | | 280-299 |
| 577 | 24 | | PK | | 5-0 | 23-32-12 | D01933 | | 6 | | | | D06666P | 42 | | | 275 |
| 577 | 24 | | PK | | 12-0 | 23-32-12 | D01933 | | 6 | | | | D06666P | 42 | | | 276-299 |
| 578 | 24 | | PK | | 5-0 | 23-32-12 | D01933 | | 19 | | | | D06666P | 9 | | | 275 |
| 578 | 24 | | PK | | 12-0 | 23-32-12 | D01933 | | 19 | | | | D06666P | 9 | | | 276-299 |
| 579 | 24 | | PK | | 5-0 | 23-32-12 | D01933 | | 23 | | | | D06666P | 28 | | | 275 |
| 579 | 24 | | PK | | 12-0 | 23-32-12 | D01933 | | 23 | | | | D06666P | 28 | | | 276-299 |
| 619 | 20 | | PA | | 12-0 | 23-32-11 | SM00013 | | | S | | | D01933 | 3 | | | 277-278 |
| 619 | 20 | | PA | | 11-0 | 23-32-11 | SM00013 | | | S | | | D01933 | 3 | | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 48

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | | | |
| 620 | 24 | | PK | | 11-0 | 23-32-11 | SM00007 | | | | S | | D02241 | 19 | | | 280-299 |
| 624B | 24 | | PW | YX | 11-0 | 23-32-13 | D01931 | | 36 | | | | D02241 | 9 | | | 280-299 |
| 624R | 24 | | PW | YX | 0-0 | 23-32-13 | D01931 | | 35 | | | | D02241 | 8 | | | 280-299 |
| 624Z | | | | YX | 0-0 | 23-32-13 | D01931 | | DED | | | | D02241 | | | FC | 280-299 |
| 625B | 24 | | PW | YY | 11-0 | 23-32-13 | D01931 | | 38 | | | | D02241 | 11 | | | 280-299 |
| 625R | 24 | | PW | YY | 0-0 | 23-32-13 | D01931 | | 37 | | | | D02241 | 10 | | | 280-299 |
| 625Z | | | | YY | 0-0 | 23-32-13 | D01931 | | DED | | | | D02241 | | | FC | 280-299 |
| 626 | 20 | | PA | | 10-0 | 23-32-21 | D02243 | | | | | FF | D06099P | 13 | | | 280-299 |
| 900 | 20 | | PA | | 3-0 | 23-32-11 | D06045J | | 20 | | | | SM00004 | | S | | 050-099, 150-155, 162-165 |
| 901 | 20 | | PA | | 5-0 | 23-32-21 | D06047J | | 2 | | | | D02243 | 40 | | * | 150, 152-199 |
| 902 | 20 | | PA | | 5-0 | 23-32-21 | D06047J | | 19 | | | | D02243 | 41 | | * | 150, 152-199 |
| 903 | 20 | | PA | | 5-0 | 23-32-21 | D02243 | | | | | FU | D06047J | 39 | | | 150, 152-199 |
| 904B | 20 | | PR | AB | 5-0 | 23-32-21 | D09311 | | 11 | | | | D01209 | 18 | | | 150, 153-156, 162-199 |
| 904B | 20 | | PR | AB | 5-0 | 23-32-21 | D09311 | | 11 | | | | D01209 | 18 | | * | 152 |
| 904B | 22 | | PR | AB | 5-0 | 23-32-21 | D09311 | | 11 | | | | D01209 | 18 | | | 157 |
| 904R | 20 | | PR | AB | 0-0 | 23-32-21 | D09311 | | 10 | | | | D01209 | 11 | | | 150, 153-156, 162-199 |
| 904R | 20 | | PR | AB | 0-0 | 23-32-21 | D09311 | | 10 | | | | D01209 | 11 | | * | 152 |
| 904R | 22 | | PR | AB | 0-0 | 23-32-21 | D09311 | | 10 | | | | D01209 | 11 | | | 157 |
| 904Z | | | | AB | 0-0 | 23-32-21 | D09311 | | | | | FD | D01209 | | | FX | 150, 152-199 |
| 905B | 20 | | PR | AC | 5-0 | 23-32-21 | D09311 | | 9 | | | | D01209 | 10 | | | 150, 153-156, 162-199 |
| 905B | 20 | | PR | AC | 5-0 | 23-32-21 | D09311 | | 9 | | | | D01209 | 10 | | * | 152 |
| 905B | 22 | | PR | AC | 5-0 | 23-32-21 | D09311 | | 9 | | | | D01209 | 10 | | | 157 |
| 905R | 20 | | PR | AC | 0-0 | 23-32-21 | D09311 | | 8 | | | | D01209 | 9 | | | 150, 153-156, 162-199 |
| 905R | 20 | | PR | AC | 0-0 | 23-32-21 | D09311 | | 8 | | | | D01209 | 9 | | * | 152 |
| 905R | 22 | | PR | AC | 0-0 | 23-32-21 | D09311 | | 8 | | | | D01209 | 9 | | | 157 |
| 905Z | | | | AC | 0-0 | 23-32-21 | D09311 | | | | | FD | D01209 | | | FX | 150, 152-199 |
| 907 | 20 | | PA | | 5-0 | 23-32-21 | D09311 | | 3 | | | | D09091J | 1 | | | 150, 152-199 |
| 908 | 20 | | PQ | AL | 5-0 | 23-32-21 | D09311 | | 1 | | | | D09091J | 2 | | | 150, 152-199 |
| 908Z | | | | AL | 0-0 | 23-32-21 | D09311 | | DED | | | | D09091J | 3 | | | 150, 152-199 |
| 909B | 20 | | PR | AF | 5-0 | 23-32-21 | D09311 | | 16 | | | | D06047J | 34 | | | 150, 152-156, 162-199 |
| 909B | 22 | | PR | AF | 5-0 | 23-32-21 | D09311 | | 16 | | | | D06047J | 34 | | | 157 |
| 909R | 20 | | PR | AF | 0-0 | 23-32-21 | D09311 | | 15 | | | | D06047J | 33 | | | 150, 152-156, 162-199 |
| 909R | 22 | | PR | AF | 0-0 | 23-32-21 | D09311 | | 15 | | | | D06047J | 33 | | | 157 |
| 909Z | | | | AF | 0-0 | 23-32-21 | D09311 | | 14 | | | | D06047J | DED | | | 150, 152-199 |
| 910 | 20 | | PA | | 5-0 | 23-32-21 | D09311 | | 2 | | | | D09091J | 4 | | | 150, 152-199 |
| 911 | 20 | | PA | | 5-0 | 23-32-21 | D09311 | | 4 | | | | D09091J | 5 | | | 150, 152-199 |
| 912 | 20 | | PA | | 5-0 | 23-32-21 | D09311 | | 5 | | | | D09091J | 6 | | | 150, 152-199 |
| 913 | 20 | | PA | | 5-0 | 23-32-21 | D09311 | | 19 | | | | D09091J | 7 | | | 150, 152-199 |

WIRE LIST
D280T132

91-21-11
Section W0040
Page 49
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0047 | 286T0047 | | | VIDEO SYSTEM-VTR/TUNER (continued) | | | | | | | | | | | | |
| 914 | 20 | PA | | 5-0 | 23-32-21 | D09311 | | CAP | Y | | D09091J | 8 | | | 150, 152-199 | |
| 915 | 20 | PQ | AG | 5-0 | 23-32-21 | D09311 | | CAP | Y | | D09091J | 9 | | | 150, 152-199 | |
| 915Z | | | AG | 0-0 | 23-32-21 | D09311 | | DED | | | D09091J | 10 | | | 150, 152-199 | |
| 916 | 20 | PA | | 5-0 | 23-32-21 | D09311 | | | 24 | | D09311 | 23 | | | 150, 152-199 | |
| 917 | 20 | PA | | 5-0 | 23-32-21 | D09312 | | | 12 | | D09091J | 11 | | | 150, 152-199 | |
| 918 | 20 | PA | | 5-0 | 23-32-21 | D09312 | | | 13 | | D09091J | 12 | | | 150, 152-199 | |
| 919 | 20 | PA | | 5-0 | 23-32-21 | D09312 | | | 14 | | D09312 | 1 | | | 150, 152-199 | |
| 920B | 22 | PR | AI | 5-0 | 23-32-21 | D09312 | | | 16 | * | D06047J | 29 | | | 150, 152-199 | |
| 920R | 22 | PR | AI | 0-0 | 23-32-21 | D09312 | | | 15 | * | D06047J | 28 | | | 150, 152-199 | |
| 920Z | | | AI | 0-0 | 23-32-21 | D09312 | | | 19 | | D06047J | DED | | | 150, 152-199 | |
| 921 | 20 | PA | | 5-0 | 23-32-21 | D09312 | | | 18 | | D09312 | 16 | * | | 150, 152-199 | |
| 922 | 20 | PA | | 5-0 | 23-32-21 | D09312 | | | 17 | | D09312 | 15 | * | | 150, 152-199 | |
| 950 | 20 | PA | | 5-0 | 23-32-21 | D02243 | | | 39 | * | D06047J | 1 | | | 150, 152-199 | |
| FRA | | | | 0-0 | 23-32-12 | D06047J | | | | FA | D06047J | 15 | | | 050-099, 150-199 | |
| FRB | | | | 0-0 | 23-32-12 | D01205 | | | | FB | D01205 | 3 | | | 050-099, 150-199 | |
| FRC | | | | 0-0 | 23-32-13 | D02241 | | | 24 | | D02241 | | | FC | 280-299 | |
| FRD | | | | 0-0 | 23-32-21 | D09311 | | | | FD | D09311 | 12 | | | 150, 152-199 | |
| FRE | | | | 0-0 | 23-32-21 | D06047J | | | 26 | | D06047J | | | FE | 050-099, 151 | |
| FRE | | | | 0-0 | 23-32-21 | D06099P | | | 26 | | D06099P | | | FE | 275-299 | |
| FRF | | | | 0-0 | 23-32-21 | D02243 | | | 27 | | D02243 | | | FF | 050-099, 151, 275-278 | |
| FRH | | | | 0-0 | 23-32-12 | D01931 | | | 17 | | D01931 | | | FH | 275-299 | |
| FRI | | | | 0-0 | 23-32-12 | D06666P | | | 38 | | D06666P | | | FI | 275-299 | |
| FRJ | | | | 0-0 | 23-32-12 | D06666P | | | 32 | | D06666P | | | FJ | 275-299 | |
| FRK | | | | 0-0 | 23-32-12 | D06666P | | | 16 | | D06666P | | | FK | 275-299 | |
| FRL | | | | 0-0 | 23-32-13 | D01673 | | | 24 | | D01673 | | | FL | 275-299 | |
| FRM | | | | 0-0 | 23-32-13 | D01651 | | | 24 | | D01651 | | | FM | 275-299 | |
| W0048 | 286T0048 | | | P6-R2-LOAD DISTRIBUTION | | | | | | | | | | | | |
| 001 | 22 | PA | | 3-7 | 25-11-21 | D06192J | | | 21 | | C00355 | A1 | D | | ALL | |
| 002 | 22 | PA | | 3-7 | 25-11-21 | D06192J | | | 22 | | C00355 | B1 | D | | ALL | |
| 003 | 22 | PA | | 3-7 | 25-11-21 | D06192J | | | 23 | | C00355 | C1 | D | | ALL | |
| 004 | 22 | PA | | 3-8 | 30-31-21 | D06192J | | | 11 | | C01116 | 2 | D | | ALL | |
| 006 | 22 | PA | | 3-7 | 30-31-23 | D06192J | | | 13 | | C01114 | 2 | D | | ALL | |
| 009 | 22 | PQ | E | 3-9 | 30-32-21 | D06192J | | | 15 | | C01141 | 2 | D | | ALL | |
| 009Z | | | E | 0-0 | 30-32-21 | D06192J | | | DED | | C01141 | DED | | | ALL | |
| 011 | 22 | PA | | 3-9 | 30-34-21 | D06192J | | | 18 | | C01123 | 2 | D | | ALL | |
| 025 | 12 | PA | | 4-2 | 21-58-15 | D05920J | | | 12 | | C00335 | C2 | D | | ALL | |
| 026 | 12 | PA | | 4-2 | 21-58-15 | D05920J | | | 11 | | C00335 | B2 | D | | ALL | |
| 027 | 12 | PA | | 4-2 | 21-58-15 | D05920J | | | 10 | | C00335 | A2 | D | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0040

Page 50

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0048 | 286T0048 | | | P6-R2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | |
| 031 | 18 | | PA | | 4-2 | 25-29-11 | TB0016F | A007 | 2 | | C00314 | C1 | D | | ALL | |
| 042 | 22 | | PA | | 3-2 | 25-29-11 | D05846J | | 13 | | TB0016F | C007 | 2 | | ALL | |
| 048 | 16 | | PA | | 4-2 | 28-22-11 | D05920J | | 1 | | C00371 | A1 | D | | ALL | |
| 049 | 16 | | PA | | 4-2 | 28-22-11 | D05920J | | 2 | | C00371 | B1 | D | | ALL | |
| 050 | 16 | | PA | | 4-2 | 28-22-11 | D05920J | | 3 | | C00371 | C1 | D | | ALL | |
| 051 | 16 | | PA | | 4-4 | 28-22-11 | D05920J | | 4 | | C00372 | A1 | D | | ALL | |
| 052 | 16 | | PA | | 4-4 | 28-22-11 | D05920J | | 5 | | C00372 | B1 | D | | ALL | |
| 053 | 16 | | PA | | 4-4 | 28-22-11 | D05920J | | 6 | | C00372 | C1 | D | | ALL | |
| 054 | 12 | | PA | | 4-4 | 28-22-12 | D06192J | | 2 | | C00370 | A2 | D | | ALL | |
| 055 | 12 | | PA | | 4-4 | 28-22-12 | D06192J | | 4 | | C00370 | B2 | D | | ALL | |
| 056 | 12 | | PA | | 4-4 | 28-22-12 | D06192J | | 6 | | C00370 | C2 | D | | ALL | |
| 057 | 24 | | PK | | 4-6 | 24-51-43 | D05846J | | 9 | | TB0014F | A015 | 2 | | ALL | |
| 058 | 24 | | PK | | 4-6 | 24-51-43 | D05846J | | 10 | | TB0014F | C015 | 2 | | ALL | |
| 059 | 24 | | PK | | 4-6 | 24-51-43 | D05846J | | 11 | | TB0014F | A016 | 2 | | ALL | |
| 063 | 20 | | PA | | 4-8 | 24-51-43 | D06430J | | 2 | | D10744 | | 13 | | ALL | |
| 064 | 20 | | PA | | 4-8 | 24-51-43 | D06430J | | 1 | | D10744 | | 9 | | ALL | |
| 065 | 20 | | PA | | 4-8 | 24-51-43 | D06430J | | 4 | | D10744 | | 4 | | ALL | |
| 066 | 20 | | PA | | 4-8 | 24-51-43 | D06430J | | 3 | | D10744 | | 2 | | ALL | |
| 067 | 20 | | PA | | 4-8 | 24-51-43 | D06430J | | 6 | | D10744 | | 12 | | ALL | |
| 068 | 20 | | PA | | 4-8 | 24-51-43 | D06430J | | 5 | | D10744 | | 8 | | ALL | |
| 069 | 24 | | PK | | 3-5 | 24-51-43 | TB0014F | A015 | 2 | | D10744 | | 3 | | ALL | |
| 070 | 20 | | PA | | 2-9 | 24-51-43 | GD02416 | S.. | 2 | | D10744 | | 18 | | ALL | |
| 071 | 24 | | PK | | 3-5 | 24-51-43 | TB0014F | C015 | 2 | | D10744 | | 10 | | ALL | |
| 072 | 20 | | PA | | 2-9 | 24-51-43 | GD02416 | D.. | 2 | | D10744 | | 19 | | ALL | |
| 074 | 24 | | PK | | 3-5 | 24-51-43 | TB0014F | C016 | 2 | | D10744 | | 14 | | ALL | |
| 075 | 20 | | PA | | 2-9 | 24-51-43 | GD02416 | D.. | 2 | | D10744 | | 15 | | ALL | |
| 076 | 20 | | PA | | 4-4 | 24-51-43 | C04269 | | 1 | D | D10744 | | 17 | | ALL | |
| 077 | 20 | | PA | | 4-2 | 24-51-43 | C04267 | | 1 | D | D10744 | | 6 | | ALL | |
| 078 | 20 | | PA | | 4-3 | 24-51-43 | C04268 | | 1 | D | D10744 | | 16 | | ALL | |
| 079 | 20 | | PA | | 2-9 | 24-51-43 | GD02416 | D.. | 2 | | D10744 | | 7 | | ALL | |
| 080 | 24 | | PK | | 3-0 | 24-51-42 | TB0016Y | C005 | BJ | | D10744 | | 1 | | ALL | |
| 081 | 24 | | PK | | 3-5 | 24-51-42 | TB0014F | A017 | 2 | | D10744 | | 5 | | ALL | |
| 082 | 12 | | PA | | 1-3 | 24-51-24 | D06430J | | 15 | | D06446J | | 1 | | ALL | |
| 083 | 12 | | PA | | 6-0 | 24-51-24 | D06430J | | 19 | | C00844 | 2 | D | * | ALL | |
| 084 | 12 | | PA | | 6-0 | 24-51-24 | C00844 | | 2 | D | D06446J | | 2 | | ALL | |
| 085 | 22 | | PA | | 3-11 | 24-51-24 | C00844 | | 1 | D | T00194 | HV2 | E | | ALL | |
| 086 | 16 | | PA | | 2-7 | 24-51-24 | T00194 | GND | E | | GD04756 | A.. | 2 | | ALL | |
| 087 | 18 | | PA | | 3-11 | 24-51-24 | T00194 | LV | E | | D06430J | | 23 | | ALL | |
| 088 | 12 | | PA | | 5-3 | 24-51-24 | D06430J | | 27 | | C01123 | 1 | D | * | ALL | |

WIRE LIST

D280T132

91-21-11
Section W0040
Page 51
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0048 | 286T0048 | | | P6-R2-LOAD DISTRIBUTION (continued) | | | | | | | | | | | |
| 089 | 12 | | PA | | 5-3 | 24-51-24 | D06446J | | 3 | | C01123 | 1 | D | * | ALL |
| 090 | 18 | | PA | | 8-6 | 24-51-24 | D06450J | | 3 | | C00327 | C2 | D | | ALL |
| 091 | 18 | | PA | | 8-6 | 24-51-24 | D06450J | | 2 | | C00327 | B2 | D | | ALL |
| 092 | 18 | | PA | | 8-6 | 24-51-24 | D06450J | | 1 | | C00327 | A2 | D | | ALL |
| 401B | 24 | | PN | A | 2-9 | 24-23-11 | D05846J | | 8 | | D00304 | 1 | | | ALL |
| 401G | 24 | | PN | A | 0-0 | 24-23-11 | D05846J | | 5 | | D00304 | 4 | | | ALL |
| 401R | 24 | | PN | A | 0-0 | 24-23-11 | D05846J | | 7 | | D00304 | 2 | | | ALL |
| 401Y | 24 | | PN | A | 0-0 | 24-23-11 | D05846J | | 6 | | D00304 | 3 | | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----------------------------|----|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0051 | 286T0051 | H1 AND P3 INSTR PNL | | | | | | | | | | | | | |
| 001 | 24 | | PV | AA | 7-1 | 22-14-11 | D04513P | | | | | | | | |
| 001Z | | | | AA | 0-0 | 22-14-11 | D04513P | DED | | | D05453P | | | | ALL |
| 002 | 24 | | PK | | 3-7 | 31-25-11 | D04556P | | | 15 | TB0243X | A004 | BJ | | ALL |
| 003 | 24 | | PK | | 3-7 | 31-25-11 | D05347P | | | 17 | TB0243X | A003 | BJ | | ALL |
| 004 | 22 | | PA | | 8-0 | 34-13-11 | D00220 | | | 3 | D04267P | | | 2 | ALL |
| 005 | 20 | | PA | | 5-4 | 34-13-11 | D00220 | | | 4 | GD03702 | D.. | 2 | | ALL |
| 006 | 20 | | PA | | 5-4 | 34-13-11 | D00220 | | | 5 | GD03702 | S.. | 2 | | ALL |
| 007 | 20 | | PA | | 6-0 | 34-13-11 | D00218 | | | 5 | GD03702 | S.. | 2 | | ALL |
| 008 | 22 | | PA | | 3-8 | 34-22-81 | D04267P | | | 1 | TB0241X | D005 | BJ | | ALL |
| 009 | 20 | | PA | | 6-4 | 34-24-11 | D00216 | | | 24 | GD03702 | S.. | 2 | | ALL |
| 010 | 24 | | PK | | 8-3 | 34-24-11 | D00216 | | | 18 | D05453P | | | 10 | ALL |
| 011 | 24 | | PK | | 8-3 | 34-24-11 | D00216 | | | 15 | D05453P | | | 13 | ALL |
| 012 | 24 | | PK | | 8-3 | 34-24-11 | D00216 | | | 16 | D05453P | | | 16 | ALL |
| 013 | 24 | | PK | | 8-3 | 34-24-11 | D00216 | | | 17 | D05453P | | | 19 | ALL |
| 014 | 24 | | PK | | 6-3 | 33-11-11 | D04984J | | | 1 | D04556P | | | 1 | ALL |
| 015 | 24 | | PK | | 5-1 | 33-11-11 | D04984J | | | 2 | TB0247Y | A003 | BJ | | ALL |
| 016 | 24 | | PK | | 10-10 | 33-11-11 | D02426 | | | 16 | TB0247Y | A003 | BJ | | ALL |
| 017 | 24 | | PK | | 3-7 | 33-11-11 | D04556P | | | 2 | TB0247Y | A003 | BJ | | ALL |
| 018 | 20 | | PA | | 1-10 | 33-11-11 | D02426 | | | 17 | GD04466 | A.. | 2 | | ALL |
| 019 | 24 | | PK | | 1-7 | 33-13-11 | D10430 | | | C3 | TB0249R | A002 | 2 | | ALL |
| 020 | 24 | | PK | | 11-8 | 33-11-11 | D04982J | | | 1 | D05347P | | | 1 | ALL |
| 021 | 24 | | PK | | 11-0 | 33-11-11 | D04982J | | | 2 | TB0247Y | A004 | BJ | | ALL |
| 022 | 24 | | PK | | 9-10 | 33-11-11 | D02678 | | | 16 | TB0247Y | A004 | BJ | | ALL |
| 023 | 24 | | PK | | 3-7 | 33-11-11 | D05347P | | | 2 | TB0247Y | A004 | BJ | | ALL |
| 024 | 20 | | PA | | 1-11 | 33-11-11 | D02678 | | | 17 | GD04464 | A.. | 2 | | ALL |
| 026 | 20 | | PA | | 8-9 | 33-11-13 | D04984J | | | 16 | D03768 | | | 2 | ALL |
| 027 | 20 | | PA | | 7-3 | 33-11-13 | D04982J | | | 16 | D03768 | | | 8 | ALL |
| 028 | 24 | | PK | | 10-4 | 33-11-13 | D04556P | | | 11 | D03768 | | | 12 | ALL |
| 029 | 20 | | PA | | 2-4 | 33-11-13 | GD04464 | | | S.. 2 | D03768 | | | 7 | ALL |
| 030 | 20 | | PA | | 2-4 | 33-11-13 | GD04464 | | | A.. 2 | D03768 | | | 11 | ALL |
| 031R | 22 | | PH | | 10-6 | 26-11-11 | D05347P | | | 16 | D04513P | | | 2 | ALL |
| 033 | 24 | | PK | | 3-7 | 73-21-14 | D05347P | | | 14 | TB0247X | A006 | BJ | | ALL |
| 034 | 16 | | PA | | 1-5 | 33-13-11 | D00212 | | | D3 | SM00009 | | | W | ALL |
| 035 | 18 | | PA | | 8-4 | 32-35-11 | D04515P | | | 2 | D05347P | | | 19 | ALL |
| 036 | 18 | | PQ | BK | 8-4 | 32-35-11 | D04515P | | | 3 | D05347P | | | 23 | ALL |
| 036Z | | | | BK | 0-0 | 32-35-11 | D04515P | | | DED | D05347P | | | DED | ALL |
| 037 | 18 | | PA | | 8-4 | 32-35-11 | D04515P | | | 4 | D05347P | | | 15 | ALL |
| 038 | 16 | | PA | | 3-7 | 33-13-11 | D00212 | | | D1 | D02688 | | | 2 | FM |
| 039 | 22 | | PQ | BN | 10-6 | 32-41-11 | D04513P | | | 3 | D04556P | | | 13 | ALL |

WIRE LIST

D280T132

91-21-11
Section W0050
Page 1
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0051 | 286T0051 | | | H1 AND P3 INSTR PNL (continued) | | | | | | | | | | | | |
| 039Z | | | | BN | 0-0 | 32-41-11 | D04513P | | DED | | | | D04556P | DED | | ALL |
| 040 | 24 | PK | | | 3-10 | 33-13-11 | TB0243Y | | A015 | BJ | | | D05347P | 8 | | ALL |
| 041 | 16 | PA | | | 5-1 | 33-13-11 | D00210 | | 9 | FM | | | SM00001 | | W | ALL |
| 042 | 18 | PA | | | 3-9 | 33-13-11 | D00210 | | 8 | DK | | | D00212 | B2 | | ALL |
| 043 | 16 | PA | | | 2-11 | 33-13-11 | D00210 | | 2 | FM | | | SM00009 | | W | ALL |
| 044 | 24 | PK | | | 3-9 | 33-13-11 | D00210 | | 12 | | | | D00212 | A2 | | ALL |
| 045 | 16 | PA | | | 2-3 | 33-13-11 | D00210 | | 11 | FM | | | GD04464 | A.. | 2 | ALL |
| 046 | 20 | PA | | | 2-3 | 33-13-11 | D00210 | | 7 | | | | GD04464 | S.. | 2 | ALL |
| 047 | 24 | PK | | | 9-8 | 33-13-11 | D02688 | | 12 | | | | TB0247Z | 14 | BJ | ALL |
| 048 | 16 | PA | | | 2-5 | 33-13-11 | D02688 | | 11 | FM | | | GD04464 | A.. | 2 | ALL |
| 049 | 20 | PA | | | 2-5 | 33-13-11 | D02688 | | 7 | | | | GD04464 | S.. | 2 | ALL |
| 050 | 20 | PA | | | 6-7 | 33-13-11 | D02688 | | 9 | | | | SP00343 | | 9 | ALL |
| 052 | 18 | PA | | | 4-9 | 33-13-11 | D00212 | | C2 | | | | SM00001 | | W | ALL |
| 053 | 24 | PK | | | 9-6 | 33-13-11 | D00212 | | A1 | | | | TB0247Z | 14 | BJ | ALL |
| 054 | 20 | PA | | | 4-9 | 33-13-11 | D00212 | | C1 | | | | SM00002 | | W | ALL |
| 057 | 24 | PK | | | 9-6 | 33-13-11 | D00212 | | X1 | | | | TB0247Z | 14 | BJ | ALL |
| 058 | 20 | PA | | | 3-11 | 33-13-11 | D00212 | | X2 | | | | GD04464 | A.. | 2 | ALL |
| 064 | 20 | PA | | | 4-10 | 33-13-11 | D00216 | | 1 | | | | SM00001 | | W | ALL |
| 065 | 20 | PA | | | 6-4 | 33-13-11 | D00216 | | 2 | | | | GD03698 | A.. | 2 | ALL |
| 066 | 20 | PA | | | 4-5 | 33-13-11 | D00218 | | 1 | | | | SM00001 | | W | ALL |
| 067 | 20 | PA | | | 5-5 | 33-13-11 | D00218 | | 2 | | | | GD03698 | A.. | 2 | ALL |
| 068 | 20 | PA | | | 4-4 | 33-13-11 | D00220 | | 1 | | | | SM00001 | | W | ALL |
| 069 | 20 | PA | | | 5-4 | 33-13-11 | D00220 | | 2 | | | | GD03698 | A.. | 2 | ALL |
| 070 | 20 | PA | | | 3-8 | 33-13-11 | D04513P | | 4 | | | | SM00002 | | W | ALL |
| 071 | 16 | PA | | | 6-7 | 33-13-11 | D02688 | | 8 | FM | | | SP00355 | | 9 | ALL |
| 072 | 22 | PQ | CV | | 1-8 | 33-13-13 | D03722 | | 12 | | | | TB0247X | C006 | BJ | ALL |
| 072Z | | | CV | | 0-0 | 33-13-13 | D03722 | | DED | | | | TB0247X | DED | | ALL |
| 073 | 16 | PA | | | 3-3 | 33-13-13 | D03722 | | 11 | FM | | | GD00073 | A.. | 2 | ALL |
| 074 | 20 | PQ | CX | | 3-3 | 33-13-13 | D03722 | | 7 | | | | GD00073 | S.. | 2 | ALL |
| 074Z | | | CX | | 0-0 | 33-13-13 | D03722 | | DED | | | | GD00073 | DED | | ALL |
| 075 | 20 | PQ | CY | | 1-10 | 33-13-13 | D03722 | | 8 | | | | TB0247Y | A001 | BJ | ALL |
| 075Z | | | CY | | 0-0 | 33-13-13 | D03722 | | DED | | | | TB0247Y | DED | | ALL |
| 076 | 12 | PA | | | 5-1 | 33-13-13 | SM00008 | | | W | | | SP00347 | | 9 | ALL |
| 077 | 18 | PA | | | 6-1 | 33-13-13 | SM00002 | | | W | | | D04515P | 9 | DK | ALL |
| 078 | 20 | PQ | DC | | 1-8 | 33-13-13 | D03722 | | 9 | | | | TB0247X | B005 | BJ | ALL |
| 078Z | | | DC | | 0-0 | 33-13-13 | D03722 | | DED | | | | TB0247X | DED | | ALL |
| 079 | 20 | PQ | DD | | 4-5 | 33-13-13 | D03722 | | 2 | | | | D06350P | 1 | | 050-099 |
| 079 | 18 | PQ | DD | | 4-5 | 33-13-13 | D03722 | | 2 | DK | | | D06350P | 1 | DK | 150-199, 275-299 |
| 079Z | | | DD | | 0-0 | 33-13-13 | D03722 | | DED | | | | D06350P | DED | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0050

Page 2

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0051 | 286T0051 | | | H1 AND P3 INSTR PNL (continued) | | | | | | | | | | | |
| 080 | 18 | PA | | 2-3 | 33-13-17 | D03732 | 11 | DK | | GD04466 | A.. | 2 | | ALL | |
| 081 | 20 | PA | | 2-3 | 33-13-17 | D03732 | 7 | | | GD04466 | S.. | 2 | | ALL | |
| 082 | 24 | PK | | 3-0 | 33-13-17 | D03732 | 12 | | | D10400 | D2 | | | ALL | |
| 083 | 18 | PA | | 0-10 | 33-13-17 | D03732 | 9 | DK | | SM00007 | | W | | ALL | |
| 084 | 18 | PA | | 9-8 | 33-13-17 | D04984J | 26 | DK | | SP00349 | | 9 | | ALL | |
| 086 | 18 | PA | | 3-0 | 33-13-17 | D03732 | 8 | DK | | D10400 | A2 | | | ALL | |
| 087 | 18 | PA | | 6-9 | 33-13-17 | D04982J | 26 | DK | | D10430 | D1 | | | ALL | |
| 089 | 18 | PA | | 3-0 | 33-13-17 | D10400 | C2 | | | D03732 | 2 | DK | | ALL | |
| 090 | 20 | PA | | 4-8 | 33-16-11 | D04513P | 10 | | | GD03700 | S.. | 2 | | ALL | |
| 091 | 24 | PK | | 10-6 | 33-16-11 | D04513P | 11 | | | D05347P | 10 | | | ALL | |
| 092 | 24 | PK | | 10-6 | 33-16-11 | D04513P | 12 | | | D05347P | 11 | | | ALL | |
| 093 | 20 | PA | | 4-8 | 33-16-11 | D04513P | 13 | | | GD03700 | D.. | 2 | | ALL | |
| 094 | 22 | PA | | 12-8 | 33-16-12 | D05347P | 20 | | | TB0245Y | A003 | BJ | | ALL | |
| 095 | 22 | PA | | 12-8 | 33-16-12 | D05347P | 21 | | | TB0245Y | A004 | BJ | | ALL | |
| 096 | 22 | PA | | 12-8 | 33-16-12 | D05347P | 22 | | | TB0245Z | 5 | BJ | | ALL | |
| 097 | 22 | PA | | 6-8 | 33-16-13 | D04513P | 14 | | | TB0245Y | A003 | BJ | | ALL | |
| 098 | 22 | PA | | 6-9 | 33-16-13 | D04513P | 15 | | | TB0245Z | 5 | BJ | | ALL | |
| 099 | 22 | PQ | DX | 10-6 | 33-16-13 | D04513P | 16 | | | D04556P | 21 | | | ALL | |
| 099Z | | | DX | 0-0 | 33-16-13 | D04513P | DED | | | D04556P | DED | | | ALL | |
| 100 | 16 | PA | | 6-5 | 33-13-11 | D00212 | D2 | | | SP00345 | | 9 | | ALL | |
| 101 | 22 | PA | | 8-8 | 33-16-15 | D04515P | 11 | | | TB0245Z | 5 | BJ | | ALL | |
| 102 | 22 | PA | | 8-7 | 33-16-15 | D04515P | 10 | | | TB0245Y | A004 | BJ | | ALL | |
| 103 | 22 | PQ | EC | 6-3 | 33-16-16 | D04984J | 21 | | | D04556P | 20 | | | ALL | |
| 103Z | | | EC | 0-0 | 33-16-16 | D04984J | DED | | | D04556P | DED | | | ALL | |
| 104 | 22 | PA | | 11-1 | 33-16-16 | D04984J | 22 | | | TB0245Z | 5 | BJ | | ALL | |
| 105 | 22 | PA | | 5-2 | 33-16-16 | D04982J | 22 | | | TB0245Z | 5 | BJ | | ALL | |
| 106 | 22 | PA | | 5-1 | 33-16-16 | D04982J | 21 | | | TB0245Y | A004 | BJ | | ALL | |
| 107 | 22 | PQ | EG | 3-6 | 33-16-12 | D04556P | 22 | | | TB0243Y | C001 | BJ | | ALL | |
| 107Z | | | EG | 0-0 | 33-16-12 | D04556P | DED | | | TB0243Y | DED | | | ALL | |
| 108 | 22 | PQ | EH | 7-8 | 33-16-15 | D04515P | 16 | | | TB0243Y | C001 | BJ | | ALL | |
| 108Z | | | EH | 0-0 | 33-16-15 | D04515P | DED | | | TB0243Y | DED | | | ALL | |
| 110R | 22 | PH | | 8-4 | 26-17-11 | D04515P | 15 | | | D05347P | 9 | | | ALL | |
| 113 | 24 | PK | | 9-7 | 33-13-11 | D00212 | A3 | | | TB0243Y | A015 | BJ | | ALL | |
| 114 | 24 | PK | | 11-6 | 33-13-17 | D10400 | X1 | | | TB0243Y | C015 | BJ | | ALL | |
| 115 | 24 | PK | | 11-6 | 33-13-17 | D10400 | D1 | | | TB0243Y | C015 | BJ | | ALL | |
| 116 | 24 | PK | | 11-6 | 33-13-17 | D10400 | D3 | | | TB0243Y | A015 | BJ | | ALL | |
| 117 | 18 | PA | | 3-8 | 33-13-17 | D10430 | D2 | | | SM00007 | | W | | ALL | |
| 119 | 18 | PA | | 8-5 | 33-13-17 | D10400 | A1 | | | SP00349 | | 9 | | ALL | |
| 120 | 18 | PA | | 8-5 | 33-13-17 | D10400 | C1 | | | SP00353 | | 9 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0050

Page 3

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0051 | 286T0051 | | | H1 AND P3 INSTR PNL (continued) | | | | | | | | | | | | | |
| 121 | 18 | PA | | 6-8 | 33-13-17 | SM00007 | | | | | W | | SP00351 | | 9 | | ALL |
| 122 | 20 | PA | | 3-2 | 33-13-17 | D10400 | | X2 | | | | | GD04466 | A.. | 2 | | ALL |
| 123 | 24 | PK | | 0-7 | 33-13-11 | TB0249R | | C002 | 2 | | | | TB0249R | A001 | 2 | | ALL |
| 124 | 24 | PK | | 9-6 | 33-13-11 | D10430 | | X1 | | | | | TB0247Z | 14 | BJ | | ALL |
| 125 | 20 | PA | | 4-0 | 33-13-11 | D10430 | | X2 | | | | | GD04464 | A.. | 2 | | ALL |
| 126 | 18 | PA | | 7-1 | 32-35-11 | D04515P | | | 1 | DK | | | GD03700 | D.. | 2 | | ALL |
| 127 | 18 | PA | | 5-2 | 33-13-11 | D06366J | | | = 1 | | | | SM00001 | | W | | ALL |
| 128 | 18 | PA | | 6-0 | 33-13-11 | D06368P | | | = 1 | | | | GD04476 | A.. | 2 | | ALL |
| 130 | 16 | PA | | 0-10 | 33-13-13 | D00212 | | | B1 | | | | SM00008 | | W | | ALL |
| 141 | 22 | PA | | 9-0 | 34-22-36 | D04515P | | | 18 | | | | D05453P | 23 | | | ALL |
| 142 | 20 | PA | | 7-1 | 34-22-36 | D04515P | | | 19 | | | | GD00071 | D.. | 2 | | ALL |
| 145 | 16 | PA | | 9-0 | 33-13-18 | D05347P | | | 27 | | | | SM00009 | | W | | ALL |
| 161 | 22 | PA | | 4-0 | 34-12-61 | TB0243X | | | D003 | BJ | | | D04556P | 12 | | | ALL |
| 201B | 24 | PL | IA | 8-3 | 34-24-11 | D00216 | | | 22 | | | | D05453P | 2 | | | ALL |
| 201R | 24 | PL | IA | 0-0 | 34-24-11 | D00216 | | | 21 | | | | D05453P | 1 | | | ALL |
| 202B | 24 | PL | IB | 8-3 | 34-24-11 | D00216 | | | 8 | | | | D05453P | 9 | | | ALL |
| 202R | 24 | PL | IB | 0-0 | 34-24-11 | D00216 | | | 7 | | | | D05453P | 8 | | | ALL |
| 203B | 24 | PL | IC | 8-3 | 34-24-11 | D00216 | | | 10 | | | | D05453P | 12 | | | ALL |
| 203R | 24 | PL | IC | 0-0 | 34-24-11 | D00216 | | | 9 | | | | D05453P | 11 | | | ALL |
| 204B | 24 | PL | ID | 8-3 | 34-24-11 | D00216 | | | 14 | | | | D05453P | 15 | | | ALL |
| 204R | 24 | PL | ID | 0-0 | 34-24-11 | D00216 | | | 13 | | | | D05453P | 14 | | | ALL |
| 205B | 24 | PL | IE | 8-3 | 34-24-11 | D00216 | | | 12 | | | | D05453P | 18 | | | ALL |
| 205R | 24 | PL | IE | 0-0 | 34-24-11 | D00216 | | | 11 | | | | D05453P | 17 | | | ALL |
| 206B | 24 | PW | IF | 9-10 | 33-11-11 | D04984J | | | 3 | | | | D02426 | 3 | | | ALL |
| 206R | 24 | PW | IF | 0-0 | 33-11-11 | D04984J | | | 9 | | | | D02426 | 9 | | | ALL |
| 206Z | | | IF | 0-0 | 33-11-11 | D04984J | | | 8 | | | | D02426 | | | FA | ALL |
| 207B | 24 | PL | IG | 9-10 | 33-11-11 | D04984J | | | 12 | | | | D02426 | 12 | | | ALL |
| 207R | 24 | PL | IG | 0-0 | 33-11-11 | D04984J | | | 13 | | | | D02426 | 13 | | | ALL |
| 208B | 24 | PL | IH | 9-10 | 33-11-11 | D04984J | | | 4 | | | | D02426 | 4 | | | ALL |
| 208R | 24 | PL | IH | 0-0 | 33-11-11 | D04984J | | | 5 | | | | D02426 | 5 | | | ALL |
| 209B | 24 | PL | II | 9-10 | 33-11-11 | D04984J | | | 6 | | | | D02426 | 6 | | | ALL |
| 209R | 24 | PL | II | 0-0 | 33-11-11 | D04984J | | | 7 | | | | D02426 | 7 | | | ALL |
| 210 | 20 | UA | | 1-6 | 33-11-11 | D02426 | | | | | | FA | GD04466 | S.. | 2 | | 050-099 |
| 210 | 20 | UA | | 1-10 | 33-11-11 | D02426 | | | | | | FA | GD04466 | S.. | 2 | | 150-199, 275-299 |
| 210B | 24 | PW | IJ | 11-6 | 33-11-11 | D04556P | | | 3 | | | | D02426 | 1 | | | ALL |
| 210R | 24 | PW | IJ | 0-0 | 33-11-11 | D04556P | | | 4 | | | | D02426 | 10 | | | ALL |
| 210Z | | | IJ | 0-0 | 33-11-11 | D02426 | | | | | | FA | D04556P | | | FB | ALL |
| 211B | 24 | PW | IK | 7-4 | 33-11-11 | D04982J | | | 3 | | | | D02678 | 3 | | | ALL |
| 211R | 24 | PW | IK | 0-0 | 33-11-11 | D04982J | | | 9 | | | | D02678 | 9 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0050

Page 4

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|------|------|--------|-------------|------|----|--|----|------------------|-----|-----|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | | | |
| W0051 | 286T0051 | | | H1 AND P3 INSTR PNL (continued) | | | | | | | | | | | | | | | | | | | |
| 211Z | | | | IK | 0-0 | 33-11-11 | D04982J | | 8 | | | | | | | D02678 | | | | FC | ALL | | |
| 212B | 24 | PL | IL | | 7-4 | 33-11-11 | D04982J | | 19 | | | | | | | D02678 | | 19 | | | ALL | | |
| 212R | 24 | PL | IL | | 0-0 | 33-11-11 | D04982J | | 20 | | | | | | | D02678 | | 20 | | | ALL | | |
| 213B | 24 | PL | IM | | 7-4 | 33-11-11 | D04982J | | 14 | | | | | | | D02678 | | 14 | | | ALL | | |
| 213R | 24 | PL | IM | | 0-0 | 33-11-11 | D04982J | | 15 | | | | | | | D02678 | | 15 | | | ALL | | |
| 214B | 24 | PL | IN | | 7-4 | 33-11-11 | D04982J | | 12 | | | | | | | D02678 | | 12 | | | ALL | | |
| 214R | 24 | PL | IN | | 0-0 | 33-11-11 | D04982J | | 13 | | | | | | | D02678 | | 13 | | | ALL | | |
| 215B | 24 | PL | IO | | 7-4 | 33-11-11 | D04982J | | 4 | | | | | | | D02678 | | 4 | | | ALL | | |
| 215R | 24 | PL | IO | | 0-0 | 33-11-11 | D04982J | | 5 | | | | | | | D02678 | | 5 | | | ALL | | |
| 216B | 24 | PL | IP | | 7-4 | 33-11-11 | D04982J | | 6 | | | | | | | D02678 | | 6 | | | ALL | | |
| 216R | 24 | PL | IP | | 0-0 | 33-11-11 | D04982J | | 7 | | | | | | | D02678 | | 7 | | | ALL | | |
| 217 | 20 | UA | | | 1-6 | 33-11-11 | D02678 | | | | | | | | | GD04464 | S.. | 2 | | | 050-099 | | |
| 217 | 20 | UA | | | 1-11 | 33-11-11 | D02678 | | | | | | | | | GD04464 | S.. | 2 | | | 150-199, 275-299 | | |
| 217B | 24 | PW | IQ | | 10-5 | 33-11-11 | D05347P | | 3 | | | | | | | D02678 | | 1 | | | ALL | | |
| 217R | 24 | PW | IQ | | 0-0 | 33-11-11 | D05347P | | 4 | | | | | | | D02678 | | 10 | | | ALL | | |
| 217Z | | | | | 0-0 | 33-11-11 | D02678 | | | | | | | | | D05347P | | | | | FC | FD | ALL |
| 222B | 24 | PL | IV | | 1-7 | 33-13-11 | D10430 | | B3 | | | | | | | TB0249R | C001 | 2 | | | ALL | | |
| 222R | 24 | PL | IV | | 0-0 | 33-13-11 | D10430 | | A3 | | | | | | | TB0249R | A001 | 2 | | | ALL | | |
| 301B | 24 | PM | MA | | 8-3 | 34-24-11 | D00216 | | 4 | | | | | | | D05453P | | 21 | | | ALL | | |
| 301R | 24 | PM | MA | | 0-0 | 34-24-11 | D00216 | | 3 | | | | | | | D05453P | | 20 | | | ALL | | |
| 301Y | 24 | PM | MA | | 0-0 | 34-24-11 | D00216 | | 5 | | | | | | | D05453P | | 22 | | | ALL | | |
| 302B | 24 | PX | MB | | 11-6 | 33-11-11 | D04556P | | 5 | | | | | | | D02426 | | 8 | | | ALL | | |
| 302R | 24 | PX | MB | | 0-0 | 33-11-11 | D04556P | | 6 | | | | | | | D02426 | | 11 | | | ALL | | |
| 302Y | 24 | PX | MB | | 0-0 | 33-11-11 | D04556P | | 7 | | | | | | | D02426 | | 18 | | | ALL | | |
| 302Z | | | | | 0-0 | 33-11-11 | D02426 | | | | | | | | | D04556P | | | | | FA | FB | ALL |
| 303B | 24 | PX | MC | | 10-5 | 33-11-11 | D05347P | | 5 | | | | | | | D02678 | | 8 | | | ALL | | |
| 303R | 24 | PX | MC | | 0-0 | 33-11-11 | D05347P | | 6 | | | | | | | D02678 | | 11 | | | ALL | | |
| 303Y | 24 | PX | MC | | 0-0 | 33-11-11 | D05347P | | 7 | | | | | | | D02678 | | 18 | | | ALL | | |
| 303Z | | | | | 0-0 | 33-11-11 | D02678 | | | | | | | | | D05347P | | | | | FC | FD | ALL |
| 304B | 24 | PM | MD | | 10-4 | 33-11-13 | D04556P | | 8 | | | | | | | D03768 | | 5 | | | ALL | | |
| 304R | 24 | PM | MD | | 0-0 | 33-11-13 | D04556P | | 9 | | | | | | | D03768 | | 6 | | | ALL | | |
| 304Y | 24 | PM | MD | | 0-0 | 33-11-13 | D04556P | | 10 | | | | | | | D03768 | | 1 | | | ALL | | |
| 305B | 24 | PM | ME | | 3-10 | 33-13-11 | D00210 | | 5 | | | | | | | D10430 | | C2 | | | ALL | | |
| 305R | 24 | PM | ME | | 0-0 | 33-13-11 | D00210 | | 6 | | | | | | | D10430 | | A2 | | | ALL | | |
| 305Y | 24 | PM | ME | | 0-0 | 33-13-11 | D00210 | | 1 | | | | | | | D10430 | | B2 | | | ALL | | |
| 306B | 24 | PM | MF | | 2-7 | 33-13-11 | D04982J | | 30 | | | | | | | SM00004 | | | | | W | ALL | |
| 306R | 24 | PM | MF | | 0-0 | 33-13-11 | D04982J | | 29 | | | | | | | SM00003 | | | | | W | ALL | |
| 306Y | 24 | PM | MF | | 0-0 | 33-13-11 | D04982J | | 31 | | | | | | | SM00005 | | | | | W | ALL | |
| 307B | 24 | PM | MG | | 4-11 | 33-13-11 | D02688 | | 5 | | | | | | | SM00004 | | | | | W | ALL | |

WIRE LIST

D280T132

91-21-11
 Section W0050
 Page 5
 May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0051 | 286T0051 | | | H1 AND P3 INSTR PNL (continued) | | | | | | | | | | | |
| 307R | 24 | PM | MG | 0-0 | 33-13-11 | D02688 | | 6 | | | SM00003 | | W | | ALL |
| 307Y | 24 | PM | MG | 0-0 | 33-13-11 | D02688 | | 1 | | | SM00005 | | W | | ALL |
| 308B | 24 | PX | MH | 6-3 | 33-13-13 | D03722 | | 5 | | | D04984J | 30 | | | ALL |
| 308R | 24 | PX | MH | 0-0 | 33-13-13 | D03722 | | 6 | | | D04984J | 29 | | | ALL |
| 308Y | 24 | PX | MH | 0-0 | 33-13-13 | D03722 | | 1 | | | D04984J | 31 | | | ALL |
| 308Z | | | MH | 0-0 | 33-13-13 | D03722 | | DED | | | D04984J | DED | | | ALL |
| 309B | 24 | PM | MI | 10-4 | 33-13-17 | D03732 | | 5 | | | TB0247X | B007 | BJ | | ALL |
| 309R | 24 | PM | MI | 0-0 | 33-13-17 | D03732 | | 6 | | | TB0247X | A008 | BJ | | ALL |
| 309Y | 24 | PM | MI | 0-0 | 33-13-17 | D03732 | | 1 | | | TB0247X | B008 | BJ | | ALL |
| 312B | 24 | PM | ML | 4-9 | 33-13-11 | SM00004 | | | W | | D10430 | C1 | | | ALL |
| 312R | 24 | PM | ML | 0-0 | 33-13-11 | SM00003 | | | W | | D10430 | A1 | | | ALL |
| 312Y | 24 | PM | ML | 0-0 | 33-13-11 | SM00005 | | | W | | D10430 | B1 | | | ALL |
| 798 | 20 | PA | | 4-9 | 33-13-11 | SP00355 | | 9 | | | D06348P | 1 | | | 050-099 |
| 798 | 18 | PA | | 4-9 | 33-13-11 | SP00355 | | 9 | | | D06348P | 1 | DK | | 150-199, 275-299 |
| FRA | | | | 0-0 | 33-11-11 | D02426 | | 21 | | | D02426 | | | FA | ALL |
| FRB | | | | 0-0 | 33-11-11 | D04556P | | 23 | | | D04556P | | | FB | ALL |
| FRC | | | | 0-0 | 33-11-11 | D02678 | | 21 | | | D02678 | | | FC | ALL |
| FRD | | | | 0-0 | 33-11-11 | D05347P | | 24 | | | D05347P | | | FD | ALL |
| PA1 | | | | 0-0 | 99-99-99 | D00212 | | G1 | | | D00212 | G3 | | | ALL |
| PA2 | | | | 0-0 | 99-99-99 | D10400 | | G1 | | | D10400 | G3 | | | ALL |
| W0052 | 286T0052 | | | P33-R1-LOAD DISTRIBUTION | | | | | | | | | | | |
| 001 | 20 | PA | | 6-0 | 24-31-11 | TB0200F | | A001 | 2 | | C00301 | A1 | D | | ALL |
| 002 | 20 | PA | | 6-0 | 24-31-11 | TB0200F | | C001 | 2 | | C00301 | B1 | D | | ALL |
| 003 | 20 | PA | | 6-0 | 24-31-11 | TB0200F | | A002 | 2 | | C00301 | C1 | D | | ALL |
| 004 | 18 | PA | | 7-10 | 24-31-41 | D04134J | | | 1 | | C00302 | A1 | D | | ALL |
| 005 | 18 | PA | | 7-10 | 24-31-41 | D04134J | | | 2 | | C00302 | B1 | D | | ALL |
| 006 | 18 | PA | | 7-10 | 24-31-41 | D04134J | | | 3 | | C00302 | C1 | D | | ALL |
| 007 | 18 | PA | | 8-9 | 21-26-11 | D05098J | | | 3 | | C00333 | A2 | D | | ALL |
| 008 | 18 | PA | | 8-9 | 21-26-11 | D05098J | | | 4 | | C00333 | B2 | D | | ALL |
| 009 | 18 | PA | | 8-9 | 21-26-11 | D05098J | | | 5 | | C00333 | C2 | D | | ALL |
| 016 | 22 | PA | | 6-2 | 52-11-11 | C00363 | | A2 | D | | TB0196X | A014 | BJ | | ALL |
| 017 | 22 | PA | | 6-2 | 52-11-11 | C00363 | | B2 | D | | TB0196X | B014 | BJ | | ALL |
| 018 | 22 | PA | | 6-2 | 52-11-11 | C00363 | | C2 | D | | TB0196X | D014 | BJ | | ALL |
| 020 | 20 | PA | | 6-6 | 30-71-23 | C01151 | | | 1 | D | TB0186Z | 7 | BJ | | 050-099, 150-199, 276-299 |
| 022 | 18 | PA | | 5-5 | 38-15-11 | TB0200F | | A008 | 2 | | C00397 | C2 | D | | ALL |
| 023 | 18 | PA | | 5-5 | 38-15-11 | TB0200F | | C008 | 2 | | C00397 | B2 | D | | ALL |
| 024 | 18 | PA | | 5-5 | 38-15-11 | TB0200F | | A009 | 2 | | C00397 | A2 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0050

Page 6

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|----------|-------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0052 | 286T0052 | | | P33-R1-LOAD DISTRIBUTION (continued) | | | | | | | | | | | |
| 025 | 18 | PA | | 8-6 | 25-29-11 | | TB5096 | 6 | E | | C00731 | 2 | D | | ALL |
| 028 | 12 | PA | | 8-0 | 24-51-52 | | TB5096 | 4 | E | | C00870 | 2 | D | | ALL |
| 029 | 20 | PA | | 6-8 | 30-71-11 | | TB0200F | | C010 | 2 | C01165 | 1 | D | | ALL |
| 030 | 18 | PA | | 6-8 | 30-71-11 | | TB0200F | | A010 | 2 | C01142 | 1 | D | | ALL |
| 031 | 18 | PA | | 5-3 | 30-71-21 | | C01149 | 2 | D | | TB0196G | 10 | 2 | | 050-099, 150-199 |
| 031 | 22 | PA | | 6-6 | 30-71-21 | | C01149 | 2 | D | | TB0186Y | C011 | BJ | | 276-299 |
| 033 | 20 | PA | | 6-7 | 30-71-23 | | C01156 | 1 | D | | TB0186Y | C004 | BJ | | 050-099, 150-199 |
| 033 | 20 | PA | | 6-7 | 30-71-23 | | C01156 | 1 | D | | TB0186X | D001 | BJ | | 276-299 |
| 034 | 20 | PA | | 5-0 | 33-31-11 | | TB0200F | | C009 | 2 | C01206 | 1 | D | | ALL |
| 036 | 24 | PK | | 4-7 | 33-21-11 | | TB0200F | | C011 | 2 | C01207 | 1 | D | | ALL |
| 037 | 16 | PA | | 7-0 | 33-21-11 | | D05098J | 1 | | | C01211 | 1 | D | | ALL |
| 038 | 16 | PA | | 7-2 | 33-21-12 | | D05098J | 9 | | | C01219 | 1 | D | | ALL |
| 039 | 22 | PA | | 4-9 | 33-22-41 | | TB0200F | | A012 | 2 | C01220 | 1 | D | | ALL |
| 040 | 20 | PA | | 4-10 | 33-22-42 | | TB0200F | | C012 | 2 | C01221 | 1 | D | | ALL |
| 041 | 16 | PA | | 7-2 | 33-21-12 | | D05098J | 8 | | | C01222 | 1 | D | | ALL |
| 042 | 20 | PA | | 5-0 | 33-22-11 | | TB0200F | | A013 | 2 | C01255 | 2 | D | | ALL |
| 043 | 20 | PA | | 4-11 | 33-27-11 | | TB0200F | | C013 | 2 | C01262 | 1 | D | | ALL |
| 044 | 18 | PA | | 7-2 | 33-21-31 | | D05098J | 13 | | | C01263 | 2 | D | | 050-099 |
| 044 | 16 | PA | | 7-2 | 33-21-31 | | D05098J | 13 | | | C01263 | 2 | D | | 150-199, 275-299 |
| 045 | 18 | PA | | 7-3 | 33-21-31 | | D05098J | 14 | | | C01265 | 2 | D | | 050-099 |
| 045 | 16 | PA | | 7-3 | 33-21-31 | | D05098J | 14 | | | C01265 | 2 | D | | 150-199, 275-299 |
| 046 | 24 | PK | | 4-10 | 33-21-31 | | TB0200F | | A014 | 2 | C01266 | 2 | D | | ALL |
| 047 | 24 | PK | | 6-5 | 77-35-11 | | TB0200F | | C014 | 2 | C01474 | 2 | D | | ALL |
| 048 | 18 | PA | | 4-11 | 33-31-11 | | TB0200F | | A015 | 2 | C01205 | 1 | D | | ALL |
| 049 | 20 | PA | | 5-1 | 33-11-14 | | TB0200F | | C018 | 2 | C01213 | 2 | D | | ALL |
| 050 | 22 | PA | | 5-3 | 33-22-21 | | C01229 | 2 | D | | TB0200F | C015 | 2 | | ALL |
| 051 | 22 | PA | | 4-8 | 33-24-11 | | TB0200F | | C016 | 2 | C01253 | 1 | D | | 050-099 |
| 051 | 16 | PA | | 4-8 | 33-24-11 | | TB0200F | | C016 | 2 | C01253 | 1 | D | | 150-199, 275-299 |
| 052 | 22 | PA | | 4-9 | 33-24-11 | | TB0200F | | A016 | 2 | C01260 | 1 | D | | 050-099 |
| 052 | 16 | PA | | 4-9 | 33-24-11 | | TB0200F | | A016 | 2 | C01260 | 1 | D | | 150-199, 275-299 |
| 053 | 16 | PA | | 5-1 | 33-31-41 | | TB0200G | 19 | 2 | | C01257 | 2 | D | | ALL |
| 054 | 20 | PA | | 4-10 | 33-22-11 | | TB0196X | | B003 | BJ | C01269 | 2 | D | | ALL |
| 055 | 22 | PA | | 4-10 | 33-24-11 | | TB0200F | | A018 | 2 | C01296 | 1 | D | | 050-099 |
| 055 | 16 | PA | | 4-10 | 33-24-11 | | TB0200F | | A018 | 2 | C01296 | 1 | D | | 150-199, 275-299 |
| 060 | 12 | PA | | 9-0 | 24-51-52 | | C00321 | | A2 | D | TB5096 | 1 | E | | ALL |
| 061 | 12 | PA | | 9-0 | 24-51-52 | | C00321 | | B2 | D | TB5096 | 2 | E | | ALL |
| 062 | 12 | PA | | 9-0 | 24-51-52 | | C00321 | | C2 | D | TB5096 | 3 | E | | ALL |
| 067 | 16 | PA | | 5-0 | 33-45-11 | | C01278 | 1 | D | | TB0196F | A009 | 2 | | ALL |
| 068 | 16 | PA | | 5-1 | 33-45-11 | | C01279 | 1 | D | | TB0196F | C009 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0050
 Page 7
 May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0052 | 286T0052 | | | P33-R1-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 071 | 22 | PA | | 5-2 | 33-51-11 | D05098J | | 2 | | | | | TB0188X | C006 | BJ | | ALL |
| 073 | 22 | PA | | 5-0 | 33-24-11 | C01258 | | 2 | D | | | | TB0200F | C002 | 2 | | ALL |
| 081 | 10 | PA | | 6-1 | 23-34-19 | C00536 | | 1 | D | | | | K00458 | D2 | C | | ALL |
| 082 | 12 | PA | | 6-8 | 23-34-17 | C00531 | | 1 | D | | | | K00458 | B2 | C | | ALL |
| 083 | 24 | PK | | 7-2 | 77-35-11 | C01475 | | 2 | D | | | | TB0188X | D019 | BJ | | ALL |
| 086 | 20 | PA | | 6-8 | 30-71-23 | C01166 | | 1 | D | | | | TB0186Y | C006 | BJ | | 276-299 |
| 087 | 20 | PA | | 6-5 | 30-71-22 | C01158 | | 1 | D | | | | TB0186Y | C010 | BJ | | 050-099, 155-199 |
| 087 | 22 | PA | | 5-2 | 30-71-22 | C01158 | | 1 | D | | | | TB0196X | C019 | BJ | | 276-299 |
| 088 | 24 | PK | | 10-0 | 21-26-11 | C00676 | | 2 | D | | | | TB0266X | A009 | BJ | | 156-157, 166-199, 277-299 |
| 091 | 12 | PA | | 8-9 | 23-34-17 | TB5096 | | 7 | E | | | | C00507 | 1 | D | | 280-299 |
| 821 | 20 | PA | | 4-11 | 30-71-22 | C01150 | | 1 | D | | | | TB0196X | A019 | BJ | | 050-099, 155-199, 276-299 |
| 825 | 20 | PA | | 5-1 | 30-71-21 | C01155 | | 1 | D | | | | TB0196X | D019 | BJ | | 050-099, 155-199 |
| 825 | 20 | PA | | 6-4 | 30-71-22 | C01155 | | 1 | D | | | | TB0186Y | C010 | BJ | | 276-299 |
| 838 | 20 | PA | | 5-0 | 30-71-22 | C01157 | | 1 | D | | | | TB0196X | B019 | BJ | | 050-099, 155-199 |
| 838 | 22 | PA | | 5-0 | 30-71-22 | C01157 | | 1 | D | | | | TB0196X | B019 | BJ | | 276-299 |
| W0054 | 286T0054 | | | P34-N1-LOAD DISTRIBUTION | | | | | | | | | | | | | |
| 001 | 20 | PA | | 6-10 | 33-26-11 | D05346J | | 9 | | | | | C01290 | 2 | D | | 050-099, 150-199 |
| 001 | 20 | PA | | 6-10 | 33-26-11 | D05346J | | 9 | | | | | C01215 | 2 | D | | 275-299 |
| 004 | 22 | PA | | 5-5 | 28-41-12 | D04860J | | 7 | | | | | C01040 | 1 | D | | ALL |
| 006 | 20 | PA | | 6-1 | 28-26-11 | D04860J | | 10 | | | | | C01042 | 1 | D | | ALL |
| 007 | 22 | PA | | 6-0 | 28-21-11 | D04860J | | 4 | | | | | C01041 | 1 | D | | ALL |
| 008 | 16 | PA | | 5-1 | 25-53-11 | D04926J | | 1 | FM | | | | C00746 | 1 | D | | ALL |
| 009 | 16 | PA | | 5-2 | 25-53-21 | D04926J | | 21 | FM | | | | C00747 | 1 | D | | ALL |
| 010 | 18 | PA | | 7-1 | 33-37-11 | D04926J | | 10 | DK | | | | C01209 | 2 | D | * | ALL |
| 011 | 16 | PA | | 7-2 | 33-37-21 | D04926J | | 27 | FM | | | | C01210 | 2 | D | | ALL |
| 014 | 16 | PA | | 7-0 | 30-71-24 | D05346J | | 7 | | | | | C01154 | 2 | D | | 050-099, 150-199 |
| 015 | 24 | PK | | 6-7 | 21-26-11 | D05346J | | 1 | | | | | C00707 | 1 | D | | ALL |
| 016 | 22 | PA | | 6-1 | 52-11-12 | D05346J | | 2 | | | | | C01408 | 1 | D | | 050-099, 150-199 |
| 016 | 20 | PA | | 6-1 | 52-11-12 | D05346J | | 2 | | | | | C01408 | 1 | D | | 275-299 |
| 017 | 18 | PA | | 6-8 | 33-31-21 | D05346J | | 4 | | | | | C01300 | 2 | D | | ALL |
| 018 | 24 | PK | | 7-3 | 52-34-12 | TB0024G | | 12 | 2 | | | | C01403 | 1 | D | | ALL |
| 028 | 24 | PK | | 10-2 | 24-28-11 | TB0024F | | A006 | 2 | | | | C00816 | 2 | D | | ALL |
| 029 | 24 | PK | | 18-8 | 24-28-11 | TB0024F | | A008 | 2 | | | | C00815 | 2 | D | | ALL |
| 030 | 22 | PA | | 9-8 | 24-41-11 | TB0024F | | C003 | 2 | | | | C00320 | A2 | D | | ALL |
| 031 | 22 | PA | | 6-2 | 28-21-13 | D04860J | | 2 | | | | | C01047 | 1 | D | | ALL |
| 032 | 22 | PA | | 9-8 | 24-41-11 | TB0024F | | C004 | 2 | | | | C00320 | B2 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0050

Page 8

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|---|-------|-------------|----------|---------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0054 | 286T0054 | P34-N1-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 033 | 22 | PA | | 9-8 | 24-41-11 | TB0024F | | C005 | 2 | | C00320 | C2 | D | | ALL |
| 034 | 18 | PA | | 7-11 | 24-28-11 | TB0024F | | C006 | 2 | | C00815 | 1 | D | | ALL |
| 035 | 18 | PA | | 8-0 | 33-31-31 | TB0024F | | A007 | 2 | | C01256 | 2 | D | | ALL |
| 036 | 16 | PA | | 7-8 | 24-41-11 | TB0024F | | A003 | 2 | | C00320 | A1 | D | | ALL |
| 037 | 16 | PA | | 7-9 | 24-41-11 | TB0024F | | A004 | 2 | | C00320 | B1 | D | *1 | ALL |
| 038 | 16 | PA | | 7-10 | 24-41-11 | TB0024F | | A005 | 2 | | C00320 | C1 | D | | ALL |
| 040 | 18 | PA | | 2-3 | 24-28-11 | C00816 | | | 1 | D | C00320 | B1 | D | *1 | ALL |
| 041 | 18 | PA | | 7-1 | 33-37-11 | D04926J | | | 24 | DK | C01209 | 2 | D | * | ALL |
| 042 | 24 | PK | | 4-6 | 24-51-61 | D05682J | | | 2 | | TB0024F | C007 | 2 | | ALL |
| 048 | 20 | PA | | 5-5 | 52-34-11 | D04926J | | | 15 | | C00360 | A1 | D | | ALL |
| 049 | 20 | PA | | 6-0 | 52-34-11 | D04926J | | | 16 | | C00360 | B1 | D | | ALL |
| 050 | 20 | PA | | 6-1 | 52-34-11 | D04926J | | | 17 | | C00360 | C1 | D | | ALL |
| 051 | 20 | PA | | 6-2 | 52-35-11 | D04926J | | | 18 | | C00361 | A1 | D | | ALL |
| 052 | 20 | PA | | 6-3 | 52-35-11 | D04926J | | | 19 | | C00361 | B1 | D | | ALL |
| 053 | 20 | PA | | 6-3 | 52-35-11 | D04926J | | | 20 | | C00361 | C1 | D | | ALL |
| 054 | 24 | PK | | 4-3 | 52-34-12 | D04926J | | | 2 | | TB0024G | 12 | 2 | | ALL |
| 055 | 24 | PK | | 4-3 | 52-34-12 | D04926J | | | 3 | | TB0024G | 12 | 2 | | ALL |
| 056 | 24 | PK | | 4-3 | 52-35-12 | D04926J | | | 4 | | TB0024G | 12 | 2 | | ALL |
| 058 | 22 | PA | | 7-4 | 73-21-19 | C01459 | | | 1 | D | TB0024D | A015 | 2 | | ALL |
| 059 | 22 | PA | | 3-10 | 73-21-19 | D08018J | | | 5 | | TB0024D | C015 | 2 | | ALL |
| 060 | 22 | PA | | 7-4 | 73-21-19 | C01459 | | | 1 | D | TB0024D | A016 | 2 | | ALL |
| 061 | 22 | PA | | 4-0 | 73-21-19 | D08016J | | | 5 | | TB0024D | C016 | 2 | | ALL |
| 066 | 20 | PA | | 6-11 | 33-26-11 | D05346J | | | 12 | | C01291 | 2 | D | | 050-099, 150-199 |
| 068 | 22 | PA | | 6-0 | 32-45-11 | C01187 | | | 2 | D | D08018J | 8 | | | 050-099, 150-156, 163-199, 275-299 |
| 068 | 22 | PA | | 6-0 | 32-45-11 | C01187 | | CAP | Y | | D08018J | 8 | | | 157-162 |
| 093 | 24 | PK | | 4-0 | 31-31-22 | D08016J | | | 6 | | TB0024G | 17 | 2 | | ALL |
| 099 | 18 | PA | | 6-10 | 38-32-11 | C01375 | | | 1 | D | D04860J | 9 | DK | | 156-157, 166-199, 275-299 |
| 102 | 18 | PA | | 6-9 | 38-32-11 | C01374 | | | 1 | D | D04860J | 8 | DK | | 156-157, 166-199, 275-299 |
| W0056 | 286T0056 | P36-L1-LOAD DISTRIBUTION | | | | | | | | | | | | | |
| 001 | 16 | PA | | 6-0 | 23-34-15 | C00533 | | | 1 | D | TB5076 | 8 | C | | ALL |
| 002 | 16 | PA | | 6-0 | 23-34-16 | C00530 | | | 1 | D | TB5076 | 11 | C | | ALL |
| 003 | 22 | PA | | 9-0 | 23-34-11 | C00546 | | | 1 | D | TB0222X | A007 | BJ | | ALL |
| 004 | 12 | PA | | 6-0 | 23-34-18 | C00541 | | | 1 | D | TB5076 | 9 | C | | ALL |
| 005 | 12 | PA | | 6-0 | 23-34-18 | C00535 | | | 1 | D | TB5076 | 10 | C | | ALL |
| 006 | 20 | PA | | 9-0 | 25-42-11 | C00734 | | | 2 | D | TB0220X | B004 | BJ | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0050
Page 9
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0056 | 286T0056 | | | P36-L1-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 006 | 20 | | PA | 8-0 | 25-42-11 | C00734 | | 2 | D | | | | TB0220X | B004 | BJ | | 150-199 |
| 006 | 20 | | PA | 13-0 | 25-42-11 | C00734 | | 2 | D | | | | TB0220X | B004 | BJ | | 275-299 |
| 007 | 22 | | PA | 9-0 | 23-31-12 | C00534 | | 1 | D | | | | TB0222X | D010 | BJ | | 050-099, 275-299 |
| 007 | 22 | | PA | 10-0 | 23-31-12 | C00534 | | 1 | D | | | | TB0222X | D010 | BJ | | 150-199 |
| 009 | 20 | | PA | 9-0 | 21-45-11 | C00663 | | 2 | D | | | | TB0222X | A001 | BJ | | ALL |
| 010 | 20 | | PA | 9-0 | 21-45-11 | C00662 | | 2 | D | | | | TB0222X | D002 | BJ | | ALL |
| 011 | 12 | | PA | 6-0 | 30-41-11 | C00391 | | A1 | D | | | | TB5076 | 12 | C | | ALL |
| 012 | 12 | | PA | 6-0 | 30-41-11 | C00391 | | B1 | D | | | | TB5076 | 13 | C | | ALL |
| 015 | 18 | | PA | 8-0 | 21-26-11 | C00334 | | A1 | D | | | | K00347 | A1 | E | | ALL |
| 016 | 18 | | PA | 8-0 | 21-26-11 | C00334 | | B1 | D | | | | K00347 | B1 | E | | ALL |
| 017 | 18 | | PA | 8-0 | 21-26-11 | C00334 | | C1 | D | | | | K00347 | C1 | E | | ALL |
| 018 | 12 | | PA | 7-0 | 21-25-11 | C00336 | | A2 | D | | | | K00415 | A2 | E | | ALL |
| 019 | 12 | | PA | 7-0 | 21-25-11 | C00336 | | B2 | D | | | | K00415 | B2 | E | | ALL |
| 01A | 08 | | PA | 6-0 | 24-54-11 | C00664 | | 2 | D | | | | TB5130 | 7 | E | | 050-099, 275-299 |
| 01A | 08 | | PA | 8-0 | 24-54-11 | C00664 | | 2 | D | | | | TB5130 | 7 | E | | 150-199 |
| 020 | 12 | | PA | 7-0 | 21-25-11 | C00336 | | C2 | D | | | | K00415 | C2 | E | | ALL |
| 024 | 12 | | PA | 5-0 | 38-32-11 | C00389 | | A2 | D | | | | TB5076 | 5 | C | | ALL |
| 025 | 12 | | PA | 5-0 | 38-32-11 | C00389 | | B2 | D | | | | TB5076 | 6 | C | | ALL |
| 026 | 12 | | PA | 5-0 | 38-32-11 | C00389 | | C2 | D | | | | TB5076 | 7 | C | | ALL |
| 028 | 24 | | PK | 10-0 | 21-44-11 | C00684 | | 1 | D | | | | TB0222X | B009 | BJ | | ALL |
| 032 | 18 | | PA | 9-0 | 28-26-11 | C00070 | | 2 | D | | | | TB0222G | 5 | 2 | | ALL |
| 035 | 20 | | PA | 9-0 | 28-26-11 | C00070 | | 1 | D | | | | TB0222X | B008 | BJ | | ALL |
| 036 | 20 | | PA | 9-0 | 28-26-11 | C00071 | | 1 | D | | | | TB0222X | D007 | BJ | | ALL |
| 044 | 16 | | PA | 8-0 | 38-13-11 | C01365 | | 2 | D | | | | TB0222G | 6 | 2 | | ALL |
| 045 | 24 | | PK | 10-0 | 36-23-11 | C01341 | | 1 | D | | | | TB0222X | C009 | BJ | | ALL |
| 046 | 24 | | PK | 10-0 | 21-43-11 | C00696 | | 1 | D | | | | TB0222X | B010 | BJ | | ALL |
| 047 | 24 | | PK | 10-0 | 21-44-21 | C00652 | | 1 | D | | | | TB0222X | C001 | BJ | | ALL |
| 048 | 20 | | PA | 9-0 | 30-41-11 | C01127 | | 2 | D | | | | TB0222X | D009 | BJ | | ALL |
| 049 | 20 | | PA | 9-0 | 30-41-11 | C01125 | | 2 | D | | | | TB0222X | A010 | BJ | | ALL |
| 050 | 18 | | PA | 9-0 | 21-24-11 | C00342 | | A1 | D | | | | TB0216F | C007 | 2 | | 050-099 |
| 050 | 18 | | PA | 8-0 | 21-24-11 | C00342 | | A1 | D | | | | TB0216F | C007 | 2 | | 150-199 |
| 051 | 18 | | PA | 9-0 | 21-24-11 | C00342 | | B1 | D | | | | TB0216F | A008 | 2 | | 050-099 |
| 051 | 18 | | PA | 8-0 | 21-24-11 | C00342 | | B1 | D | | | | TB0216F | A008 | 2 | | 150-199 |
| 052 | 18 | | PA | 9-0 | 21-24-11 | C00342 | | C1 | D | | | | TB0216F | C008 | 2 | | 050-099 |
| 052 | 18 | | PA | 8-0 | 21-24-11 | C00342 | | C1 | D | | | | TB0216F | C008 | 2 | | 150-199 |
| 062 | 22 | | PA | 8-0 | 21-45-21 | C00343 | | A2 | D | | | | TB0272X | A013 | BJ | | 050-099, 150-156, 162-166, 275-276 |
| 062 | 20 | | PA | 8-0 | 21-45-21 | C00343 | | A2 | D | | | | TB0272X | A013 | BJ | | 157, 167-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0050

Page 10

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0056 | 286T0056 | | | P36-L1-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | |
| 063 | 22 | | PA | 8-0 | 21-45-21 | C00343 | B2 | D | | TB0272X | B013 | BJ | | 050-099, 150-156, 162-166, 275-276 | | |
| 063 | 20 | | PA | 8-0 | 21-45-21 | C00343 | B2 | D | | TB0272X | B013 | BJ | | 157, 167-199, 277-299 | | |
| 064 | 22 | | PA | 9-0 | 21-66-11 | C00916 | 2 | D | | TB0318X | A035 | BJ | | 050-099 | | |
| 064 | 22 | | PA | 12-0 | 21-66-11 | C00916 | 2 | D | | TB0318X | A035 | BJ | | 162-199 | | |
| 065 | 20 | | PA | 9-0 | 21-66-11 | C00400 | A1 | D | | TB0318X | A011 | BJ | | 050-099 | | |
| 065 | 20 | | PA | 12-0 | 21-66-11 | C00400 | A1 | D | | TB0318X | A011 | BJ | | 162-199 | | |
| 066 | 20 | | PA | 12-0 | 21-66-11 | C00400 | B1 | D | | TB0318X | B011 | BJ | | 050-099, 162-199 | | |
| 067 | 20 | | PA | 12-0 | 21-66-11 | C00400 | C1 | D | | TB0318X | C011 | BJ | | 050-099, 162-199 | | |
| 069 | 22 | | PA | 13-0 | 21-66-11 | C00917 | 2 | D | | TB0302Y | C027 | BJ | | 050-099 | | |
| 069 | 22 | | PA | 12-0 | 21-66-11 | C00917 | 2 | D | | TB0302Y | C027 | BJ | | 162-199 | | |
| 070 | 20 | | PA | 13-0 | 21-66-11 | C00401 | A1 | D | | TB0318X | B035 | BJ | | 050-099 | | |
| 070 | 20 | | PA | 12-0 | 21-66-11 | C00401 | A1 | D | | TB0318X | B035 | BJ | | 162-199 | | |
| 071 | 20 | | PA | 12-0 | 21-66-11 | C00401 | B1 | D | | TB0318X | C035 | BJ | | 050-099, 162-199 | | |
| 072 | 20 | | PA | 12-0 | 21-66-11 | C00401 | C1 | D | | TB0318X | D035 | BJ | | 050-099, 162-199 | | |
| 073 | 24 | | PK | 13-0 | 21-66-11 | C00915 | 2 | D | | TB0076Z | 13 | BJ | | 050-099 | | |
| 073 | 22 | | PA | 13-0 | 21-66-11 | C00915 | 2 | D | | TB0076Z | 13 | BJ | | 162-199 | | |
| 074 | 22 | | PA | 13-0 | 21-66-31 | C00919 | 2 | D | | TB0222X | D013 | BJ | | 050-099 | | |
| 074 | 22 | | PA | 9-0 | 21-66-31 | C00919 | 2 | D | | TB0222X | D013 | BJ | | 150, 152-199 | | |
| 075 | 20 | | PA | 13-0 | 21-66-31 | C00403 | A2 | D | | TB0222X | A018 | BJ | | 050-099 | | |
| 075 | 20 | | PA | 9-0 | 21-66-31 | C00403 | A2 | D | | TB0222X | A018 | BJ | | 150, 152-199 | | |
| 076 | 20 | | PA | 13-0 | 21-66-31 | C00403 | B2 | D | | TB0222X | D017 | BJ | | 050-099 | | |
| 076 | 20 | | PA | 9-0 | 21-66-31 | C00403 | B2 | D | | TB0222X | D017 | BJ | | 150, 152-199 | | |
| 077 | 20 | | PA | 13-0 | 21-66-31 | C00403 | C2 | D | | TB0222X | C017 | BJ | | 050-099 | | |
| 077 | 20 | | PA | 9-0 | 21-66-31 | C00403 | C2 | D | | TB0222X | C017 | BJ | | 150, 152-199 | | |
| 078 | 22 | | PA | 9-0 | 21-66-31 | C00922 | 2 | D | * | SP04074 | | W | | 050-099, 150, 152-199 | | |
| 079 | 22 | | PA | 12-0 | 21-66-31 | C00922 | 2 | D | * | TB0318X | A036 | BJ | | 050-099 | | |
| 079 | 22 | | PA | 13-0 | 21-66-31 | C00922 | 2 | D | * | TB0318X | A036 | BJ | | 150, 152-199 | | |
| 080 | 20 | | PA | 10-0 | 21-66-31 | C00406 | A2 | D | | TB0222X | D018 | BJ | | 050-099 | | |
| 080 | 20 | | PA | 9-0 | 21-66-31 | C00406 | A2 | D | | TB0222X | D018 | BJ | | 150, 152-199 | | |
| 081 | 20 | | PA | 10-0 | 21-66-31 | C00406 | B2 | D | | TB0222X | C018 | BJ | | 050-099 | | |
| 081 | 20 | | PA | 9-0 | 21-66-31 | C00406 | B2 | D | | TB0222X | C018 | BJ | | 150, 152-199 | | |
| 082 | 20 | | PA | 10-0 | 21-66-31 | C00406 | C2 | D | | TB0222X | B018 | BJ | | 050-099 | | |
| 082 | 20 | | PA | 9-0 | 21-66-31 | C00406 | C2 | D | | TB0222X | B018 | BJ | | 150, 152-199 | | |
| 084 | 22 | | PA | 12-0 | 21-66-11 | C00400 | C1 | D | | TB0318X | C012 | BJ | | 164-199 | | |
| W0057 | 286T0057 | | | PURSER STATION | | | | | | | | | | | | |
| 001 | 22 | | PA | 7-0 | 33-21-21 | D13444J | 1 | | | D12034 | 7 | | | 150-199 | | |
| 002 | 22 | | PA | 7-0 | 33-21-21 | D13444J | 2 | | | D12034 | 5 | | | 150-199 | | |

WIRE LIST
D280T132

91-21-11
Section W0050
Page 11
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|-----|---|--|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0057 | 286T0057 | | | PURSER STATION (continued) | | | | | | | | | | | | | | | |
| 003 | 22 | | PA | | 7-0 | 33-21-21 | D13444J | | | | 3 | | | | D12034 | 15 | | | 150-199 |
| 004 | 20 | | PA | | 7-0 | 33-21-21 | D13444J | | | | 4 | | | | D12034 | 19 | | | 150-199 |
| 005 | 22 | | PA | | 7-0 | 33-21-21 | D13444J | | | | 5 | | | | D12034 | 18 | | | 150-199 |
| 006 | 24 | | PK | | 7-0 | 33-21-31 | D13444J | | | | 6 | | | | D12034 | 1 | | | 150-199 |
| 008 | 24 | | PK | | 7-0 | 33-21-31 | D13444J | | | | 8 | | | | D12034 | 12 | | | 150-199 |
| 009 | 24 | | PK | | 7-0 | 33-21-31 | D13444J | | | | 9 | | | | D12034 | 14 | | | 150-199 |
| 011 | 20 | | PA | | 7-0 | 33-21-31 | D13444J | | | | 11 | | | | D12034 | 39 | | | 150-199 |
| 012 | 20 | | PA | | 7-0 | 33-21-31 | D13444J | | | | 12 | | | | D12034 | CAP | Y | | 150, 153-154 |
| 012 | 20 | | PA | | 7-0 | 33-21-31 | D13444J | | | | 12 | | | | D12034 | 36 | | | 151-152 |
| 012 | 24 | | PK | | 7-0 | 33-21-31 | D13444J | | | | 12 | | | | D12034 | CAP | Y | | 155-199 |
| 013 | 22 | | PA | | 7-0 | 33-22-32 | D13444J | | | | 13 | | | | D13528 | E | | | 150-199 |
| 014 | 20 | | PA | | 7-0 | 33-22-32 | D13444J | | | | 14 | | | | D13528 | G | | | 150-199 |
| 015 | 20 | | PA | | 2-0 | 33-22-32 | D13444J | | | | 15 | | | | SM00004 | | S | | 150-199 |
| 016 | 20 | | PA | | 3-0 | 33-22-32 | D12034 | | | | 37 | | | | D13528 | A | | | 150-199 |
| 017 | 20 | | PA | | 3-0 | 33-22-32 | D12034 | | | | 38 | | | | D13528 | F | | | 150-199 |
| 018 | 22 | | PA | | 8-0 | 33-24-12 | D13444J | | | | 16 | | | | L01137 | FSB | C | | 050-099, 150-199 |
| 019 | 20 | | PA | | 8-0 | 33-24-12 | D13444J | | | | 17 | | | | L01137 | GND | C | | 050-099, 150-199 |
| 020 | 22 | | PA | | 8-0 | 33-24-12 | D13444J | | | | 18 | | | | L01137 | NS | C | | 050-099, 150-199 |
| 021 | 20 | | PA | | 7-0 | 33-21-11 | D13444J | | | | 21 | | | | D12034 | 10 | | | 150-199 |
| 022 | 24 | | PK | | 7-0 | 33-21-11 | D13444J | | | | 22 | | | | D12034 | 8 | | | 150-199 |
| 023 | 24 | | PK | | 7-0 | 33-21-11 | D13444J | | | | 23 | | | | D12034 | 2 | | | 150-199 |
| 024 | 20 | | PA | | 7-0 | 33-21-11 | D13444J | | | | 24 | | | | D12034 | 6 | | | 150-199 |
| 025 | 24 | | PK | | 7-0 | 33-21-11 | D13444J | | | | 25 | | | | D12034 | 20 | | | 150-199 |
| 026 | 24 | | PK | | 7-0 | 33-21-11 | D13444J | | | | 26 | | | | D12034 | 23 | | | 150-199 |
| 027 | 24 | | PK | | 7-0 | 33-21-11 | D13444J | | | | 27 | | | | D12034 | 21 | | | 150-199 |
| 028 | 24 | | PK | | 7-0 | 33-21-11 | D13444J | | | | 28 | | | | D12034 | 22 | | | 150-199 |
| 029 | 24 | | PK | | 7-0 | 33-21-12 | D13444J | | | | 29 | | | | D12034 | 24 | | | 150-199 |
| 030 | 24 | | PK | | 7-0 | 33-21-12 | D13444J | | | | 30 | | | | D12034 | 25 | | | 150-199 |
| 031 | 24 | | PK | | 7-0 | 33-21-12 | D13444J | | | | 31 | | | | D12034 | 26 | | | 150-199 |
| 032 | 24 | | PK | | 7-0 | 33-21-12 | D13444J | | | | 32 | | | | D12034 | 27 | | | 150-199 |
| 033 | 24 | | PK | | 7-0 | 33-21-12 | D13444J | | | | 33 | | | | D12034 | 13 | | | 150-199 |
| 034 | 24 | | PK | | 7-0 | 33-21-12 | D13444J | | | | 34 | | | | D12034 | 16 | | | 150-199 |
| 035 | 24 | | PK | | 7-0 | 33-21-12 | D13444J | | | | 35 | | | | D12034 | 17 | | | 150-199 |
| 036 | 24 | | PK | | 7-0 | 33-21-12 | D13444J | | | | 36 | | | | D12034 | 28 | | | 150-199 |
| 039 | 22 | | PA | | 7-0 | 33-22-42 | D13444J | | | | 39 | | | | D12034 | 35 | | | 050-099, 150-199 |
| 040 | 22 | | PA | | 7-0 | 33-22-42 | D13444J | | | | 40 | | | | D12034 | 34 | | | 050-099, 150-199 |
| 042 | 22 | | PA | | 7-0 | 23-42-11 | D13444J | | | | 42 | | | | D12034 | 41 | | | 050-099, 150-199 |
| 043 | 22 | | PA | | 7-0 | 33-22-41 | D13444J | | | | 43 | | | | D12034 | 4 | | | 050-099, 150-199 |
| 044 | 22 | | PA | | 7-0 | 33-22-41 | D13444J | | | | 44 | | | | D12034 | 11 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0050

Page 12

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0057 | 286T0057 | | | PURSER STATION (continued) | | | | | | | | | | | |
| 045 | 22 | | PA | | 7-0 | 33-22-41 | D13444J | | 45 | | D12034 | | 3 | | 050-099, 150-199 |
| 046 | 22 | | PA | | 7-0 | 33-22-41 | D13444J | | 46 | | D12034 | | 9 | | 050-099, 150-199 |
| 066 | 20 | | PA | | 7-0 | 33-22-32 | D13528 | | H | | SM00004 | | | S | 150-199 |
| 067 | 20 | | PA | | 7-0 | 33-26-21 | D13444J | | 47 | | D12034 | | 30 | | 150-157, 167-199 |
| 067 | 20 | | PA | | 7-0 | 23-31-13 | D13444J | | 47 | | D12034 | | 30 | | 162-166 |
| 068 | 20 | | PA | | 7-0 | 33-26-21 | D13444J | | 48 | | D12034 | | 31 | | 150-157, 167-199 |
| 068 | 20 | | PA | | 7-0 | 23-31-13 | D13444J | | 48 | | D12034 | | 31 | | 162-166 |
| 069 | 20 | | PA | | 7-0 | 33-26-21 | D13444J | | 49 | | D12034 | | 32 | | 150-157, 167-199 |
| 069 | 20 | | PA | | 7-0 | 23-31-13 | D13444J | | 49 | | D12034 | | 32 | | 162-166 |
| 070 | 20 | | PA | | 7-0 | 33-26-21 | D13444J | | 50 | | D12034 | | 33 | | 150-157, 167-199 |
| 070 | 20 | | PA | | 7-0 | 23-31-13 | D13444J | | 50 | | D12034 | | 33 | | 162-166 |
| 071 | 20 | | PA | | 13-0 | 33-22-32 | L01144 | | = G | E | SM00004 | | | S | 150-199 |
| 072 | 20 | | PA | | 10-0 | 33-26-21 | D12034 | | 40 | | D13444J | | 7 | | 150, 153-155 |
| 072 | 20 | | PA | | 10-0 | 33-26-21 | D12034 | | 40 | | D13444J | | 7 | * | 151-152 |
| 072 | 20 | | PA | | 7-0 | 33-26-21 | D12034 | | 40 | | D13444J | | 7 | | 156-157, 167-199 |
| 072 | 20 | | PA | | 10-0 | 23-31-13 | D12034 | | 40 | | D13444J | | 7 | | 162-165 |
| 072 | 20 | | PA | | 7-0 | 23-31-13 | D12034 | | 40 | | D13444J | | 7 | | 166 |
| 900 | 20 | | PA | | 7-0 | 33-26-21 | D12034 | | 40 | | D13444J | | 51 | * | 151-152 |
| 901 | 20 | | PA | | 3-0 | 33-22-32 | D12034 | | CAP | Y | D13528 | | D | | 150, 153-199 |
| A-A | | | | | 14-0 | 33-22-32 | L01144 | | WHT | | D13528 | | B | | 150-199 |
| A-B | | | | | 14-0 | 33-22-32 | L01144 | | WHT | | D13528 | | C | | 150-199 |
| A-C | | | | | 14-0 | 33-22-32 | L01144 | | BLK | | D13528 | | J | | 150-199 |
| A-D | | | | | 14-0 | 33-22-32 | L01144 | | BLK | | D13528 | | K | | 150-199 |
| W0058 | 286T0058 | | | P37-LOAD DISTRIBUTION | | | | | | | | | | | |
| 001 | 12 | | PA | | 7-0 | 38-32-11 | C00388 | | A1 | D | TB5078 | | 5 | C | ALL |
| 002 | 12 | | PA | | 7-0 | 38-32-11 | C00388 | | B1 | D | TB5078 | | 6 | C | ALL |
| 003 | 12 | | PA | | 7-0 | 38-32-11 | C00388 | | C1 | D | TB5078 | | 7 | C | ALL |
| 004 | 22 | | PA | | 12-0 | 33-21-21 | C01204 | | 1 | D | TB0192F | C003 | 2 | | 050-099 |
| 004 | 22 | | PA | | 10-0 | 33-21-21 | C01204 | | 1 | D | TB0192F | C003 | 2 | | 150-199, 275-299 |
| 005 | 12 | | PA | | 10-0 | 24-51-24 | C01204 | | 2 | D | TB5078 | | 11 | C | 050-099 |
| 005 | 12 | | PA | | 8-0 | 24-51-24 | C01204 | | 2 | D | TB5078 | | 11 | C | 150-199, 275-299 |
| 013 | 16 | | PA | | 12-0 | 23-34-11 | C00542 | | 2 | D | TB0190F | A002 | 2 | | 050-099 |
| 013 | 16 | | PA | | 10-0 | 23-34-11 | C00542 | | 2 | D | TB0190F | A002 | 2 | | 150-199, 275-299 |
| 014 | 16 | | PA | | 12-0 | 23-34-11 | C00543 | | 2 | D | TB0190F | C002 | 2 | | 050-099 |
| 014 | 16 | | PA | | 10-0 | 23-34-11 | C00543 | | 2 | D | TB0190F | C002 | 2 | | 150-199, 275-299 |
| 015 | 12 | | PA | | 7-0 | 21-25-21 | C00337 | | A1 | D | TB5078 | | 8 | C | ALL |
| 016 | 12 | | PA | | 7-0 | 21-25-21 | C00337 | | B1 | D | TB5078 | | 9 | C | ALL |
| 017 | 12 | | PA | | 7-0 | 21-25-21 | C00337 | | C1 | D | TB5078 | | 10 | C | ALL |

WIRE LIST

D280T132

91-21-11

Section W0050

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0058 | 286T0058 | | | P37-LOAD DISTRIBUTION (continued) | | | | | | | | | | | | |
| 018 | 20 | | PA | 10-0 | 21-45-11 | C00699 | 2 | D | | | | TB0192X | A008 | BJ | | ALL |
| 019 | 20 | | PA | 10-0 | 21-45-11 | C00700 | 2 | D | | | | TB0192X | B008 | BJ | | ALL |
| 026 | 16 | | PA | 9-0 | 38-13-11 | C01366 | 2 | D | | | | TB0210F | C008 | 2 | | 050-099 |
| 026 | 16 | | PA | 9-0 | 38-13-11 | C01366 | 2 | D | | | | TB0210G | 5 | 2 | | 150-199, 275-299 |
| 029 | 20 | | PA | 12-0 | 23-32-11 | C00549 | 2 | D | | | | TB0192Y | A015 | BJ | | 050-099 |
| 029 | 20 | | PA | 10-0 | 23-32-11 | C00549 | 2 | D | | | | TB0192Y | A015 | BJ | | 150-199 |
| 029 | 20 | | PA | 12-0 | 23-32-11 | C01550 | 2 | D | | | | TB0192Y | A015 | BJ | | 275-299 |
| 030 | 20 | | PA | 12-0 | 23-32-11 | C00550 | 2 | D | | | | TB0192X | A018 | BJ | | 050-099 |
| 030 | 20 | | PA | 10-0 | 23-32-11 | C00550 | 2 | D | | | | TB0192X | A018 | BJ | | 150-199 |
| 031 | 20 | | PA | 12-0 | 23-32-11 | C00555 | 2 | D | | | | TB0192X | B018 | BJ | | 050-099 |
| 031 | 20 | | PA | 10-0 | 23-32-11 | C00555 | 2 | D | | | | TB0192X | B018 | BJ | | 150-199 |
| 033 | 22 | | PA | 8-0 | 21-26-21 | C00344 | | A1 | D | | | TB0274X | B012 | BJ | | ALL |
| 034 | 22 | | PA | 9-0 | 21-26-21 | C00344 | | B1 | D | | | TB0192X | D019 | BJ | | ALL |
| 035 | 22 | | PA | 8-0 | 21-26-21 | C00344 | | C1 | D | | | TB0274X | A012 | BJ | | ALL |
| 039 | 20 | | PA | 9-0 | 30-41-12 | C01124 | 1 | D | | | | TB0192X | C011 | BJ | | ALL |
| 040 | 20 | | PA | 9-0 | 30-41-12 | C01126 | 1 | D | | | | TB0192X | D011 | BJ | | ALL |
| 041 | 22 | | PA | 10-0 | 30-71-21 | C01149 | 1 | D | | | | TB0190F | A017 | 2 | | 275 |
| 042 | 22 | | PA | 10-0 | 30-71-22 | C01157 | 1 | D | | | | TB0190X | D014 | BJ | | 275 |
| 043 | 20 | | PA | 10-0 | 30-71-22 | C01150 | 1 | D | | | | TB0190X | C018 | BJ | | 275 |
| 044 | 20 | | PA | 10-0 | 30-71-22 | C01155 | 1 | D | | | | TB0190X | C019 | BJ | | 275 |
| 045 | 22 | | PA | 10-0 | 30-71-22 | C01158 | 1 | D | | | | TB0190X | B013 | BJ | | 275 |
| 046 | 20 | | PA | 10-0 | 30-71-23 | C01151 | 1 | D | | | | TB0212X | A001 | BJ | | 275 |
| 047 | 20 | | PA | 10-0 | 30-71-23 | C01156 | 1 | D | | | | TB0212X | B001 | BJ | | 275 |
| 050 | 16 | | PA | 12-0 | 33-45-11 | C01275 | 1 | D | | | | TB0190F | A009 | 2 | | ALL |
| 051 | 16 | | PA | 12-0 | 33-45-11 | C01282 | 1 | D | | | | TB0190F | C009 | 2 | | 050-099 |
| 051 | 16 | | PA | 11-0 | 33-45-11 | C01282 | 1 | D | | | | TB0190F | C009 | 2 | | 150-199, 275-299 |
| 056 | 16 | | PA | 8-0 | 38-13-11 | C01373 | 2 | D | | | | TB0210G | 8 | 2 | | 162-199 |
| 057 | 20 | | PA | 8-0 | 30-71-23 | C01166 | 2 | D | | | | TB0212X | C001 | BJ | | 275 |
| 072 | 22 | | PA | 14-0 | 21-66-21 | C00918 | 2 | D | | | | TB0320X | A005 | BJ | | 050-099 |
| 072 | 22 | | PA | 13-0 | 21-66-21 | C00918 | 2 | D | | | | TB0320X | A005 | BJ | | 162-199 |
| 073 | 18 | | PA | 12-0 | 21-66-21 | C00402 | | A2 | D | | | TB0320F | C007 | 2 | | 050-099 |
| 073 | 18 | | PA | 13-0 | 21-66-21 | C00402 | | A2 | D | | | TB0320F | C007 | 2 | | 162-199 |
| 074 | 18 | | PA | 12-0 | 21-66-21 | C00402 | | B2 | D | | | TB0320F | A008 | 2 | | 050-099 |
| 074 | 18 | | PA | 13-0 | 21-66-21 | C00402 | | B2 | D | | | TB0320F | A008 | 2 | | 162-199 |
| 075 | 18 | | PA | 12-0 | 21-66-21 | C00402 | | C2 | D | | | TB0320F | C008 | 2 | | 050-099 |
| 075 | 18 | | PA | 13-0 | 21-66-21 | C00402 | | C2 | D | | | TB0320F | C008 | 2 | | 162-199 |
| 076 | 22 | | PA | 13-0 | 21-66-21 | C00921 | 2 | D | | | | SP04066 | | W | | 050-099 |
| 076 | 22 | | PA | 12-0 | 21-66-21 | C00921 | 2 | D | | | | SP04066 | | W | | 162-199 |
| 077 | 22 | | PA | 13-0 | 21-66-21 | C00921 | 2 | D | | | | TB0320X | B005 | BJ | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W0050

Page 14

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|---------|-------|------|------|-----------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0058 | 286T0058 | | | P37-LOAD DISTRIBUTION (continued) | | | | | | | | | | | |
| 078 | 20 | PA | | | 12-0 | 21-66-21 | C00405 | A1 | D | | TB0320X | C005 | BJ | | 050-099 |
| 078 | 20 | PA | | | 13-0 | 21-66-21 | C00405 | A1 | D | | TB0320X | C005 | BJ | | 162-199 |
| 079 | 20 | PA | | | 12-0 | 21-66-21 | C00405 | B1 | D | | TB0320X | D005 | BJ | | 050-099 |
| 079 | 20 | PA | | | 8-0 | 21-66-21 | C00405 | B1 | D | | TB0320X | D005 | BJ | | 162-199 |
| 080 | 20 | PA | | | 12-0 | 21-66-21 | C00405 | C1 | D | | TB0210Y | A003 | BJ | | 050 |
| 080 | 20 | PA | | | 12-0 | 21-66-21 | C00405 | C1 | D | | TB0210X | D003 | BJ | | 051-099 |
| 080 | 20 | PA | | | 8-0 | 21-66-21 | C00405 | C1 | D | | TB0210X | D003 | BJ | | 162-199 |
| 081 | 22 | PA | | | 9-0 | 21-66-41 | C00920 | | 2 D | | TB0190X | D004 | BJ | | 050-099 |
| 081 | 22 | PA | | | 8-0 | 21-66-41 | C00920 | | 2 D | | TB0190X | D004 | BJ | | 150, 152-199 |
| 082 | 18 | PA | | | 12-0 | 21-66-41 | C00404 | A2 | D | | TB0320F | A007 | 2 | | 050-099 |
| 082 | 18 | PA | | | 13-0 | 21-66-41 | C00404 | A2 | D | | TB0320F | A007 | 2 | | 150, 152-199 |
| 083 | 18 | PA | | | 12-0 | 21-66-41 | C00404 | B2 | D | | TB0190F | C017 | 2 | | 050-099 |
| 083 | 18 | PA | | | 8-0 | 21-66-41 | C00404 | B2 | D | | TB0190F | C017 | 2 | | 150, 152-199 |
| 084 | 18 | PA | | | 12-0 | 21-66-41 | C00404 | C2 | D | | TB0192F | A003 | 2 | | 050-099 |
| 084 | 18 | PA | | | 8-0 | 21-66-41 | C00404 | C2 | D | | TB0192F | A003 | 2 | | 150, 152-199 |
| 085 | 22 | PA | | | 12-0 | 21-66-41 | C00923 | | 2 D | | SP04082 | | W | | 050-099, 150, 152-199 |
| 086 | 22 | PA | | | 12-0 | 21-66-41 | C00923 | | 2 D | | TB0210Y | C003 | BJ | | 050 |
| 086 | 22 | PA | | | 12-0 | 21-66-41 | C00923 | | 2 D | | TB0210X | A003 | BJ | | 051-099 |
| 086 | 22 | PA | | | 8-0 | 21-66-41 | C00923 | | 2 D | | TB0210X | A003 | BJ | | 150, 152-199 |
| 087 | 20 | PA | | | 12-0 | 21-66-41 | C00407 | A1 | D | | TB0190X | B019 | BJ | | 050-099 |
| 087 | 20 | PA | | | 8-0 | 21-66-41 | C00407 | A1 | D | | TB0190X | B019 | BJ | | 150, 152-199 |
| 088 | 20 | PA | | | 12-0 | 21-66-41 | C00407 | B1 | D | | TB0190X | B018 | BJ | | 050-099 |
| 088 | 20 | PA | | | 8-0 | 21-66-41 | C00407 | B1 | D | | TB0190X | B018 | BJ | | 150, 152-199 |
| 089 | 20 | PA | | | 12-0 | 21-66-41 | C00407 | C1 | D | | TB0190X | A018 | BJ | | 050-099 |
| 089 | 20 | PA | | | 8-0 | 21-66-41 | C00407 | C1 | D | | TB0190X | A018 | BJ | | 150, 152-199 |
| 201B | 12 | PB | A | | 6-0 | 30-41-12 | C00392 | B2 | D | | TB5078 | 1 | C | | ALL |
| 201R | 12 | PB | A | | 0-0 | 30-41-12 | C00392 | C2 | D | | TB5078 | 2 | C | | ALL |
| 50A | 18 | PA | | | 15-0 | 23-32-31 | C01551 | | 1 D | | TB0084F | A005 | 2 | | 275-299 |
| 50B | 18 | PA | | | 15-0 | 23-32-41 | C01552 | | 1 D | | TB0084F | C005 | 2 | | 275-299 |
| 50C | 18 | PA | | | 15-0 | 23-32-51 | C01553 | | 1 D | | TB0084F | A006 | 2 | | 275-299 |
| 50D | 18 | PA | | | 15-0 | 23-32-61 | C01554 | | 1 D | | TB0084F | C006 | 2 | | 275-299 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0060 | 286T0060 | | | P5 & P61-A2-PILOT OVHD & RIGHT SIDE PNL | | | | | | | | | | | | | |
| 001 | 20 | | PA | 8-1 | 33-13-16 | D01394 | | 1 | | | | | TB0068H | 6 | 2 | | ALL |
| 002 | 20 | | PA | 7-4 | 33-13-16 | D01394 | | 2 | | | | | GD00110 | A.. | 2 | | ALL |
| 003 | 22 | | PQ | AC | 8-1 | 33-16-17 | TB0068Z | | 13 | BJ | | | D01394 | 3 | | | ALL |
| 003Z | | | AC | 0-0 | 33-16-17 | TB0068Z | | DED | | | | | D01394 | DED | | | ALL |
| 004 | 22 | | PQ | AD | 8-1 | 33-16-17 | TB0068Z | | 16 | BJ | | | D01394 | 4 | | | ALL |
| 004Z | | | AD | 0-0 | 33-16-17 | TB0068Z | | DED | | | | | D01394 | DED | | | ALL |
| 005 | 22 | | PA | 8-1 | 49-61-11 | D01394 | | 5 | | | | | TB0064X | A017 | BJ | | ALL |
| 011 | 22 | | PA | 15-1 | 49-61-11 | D01394 | | 11 | | | | | D04796J | 31 | | | ALL |
| 013 | 24 | | PK | 11-0 | 24-27-41 | D04796J | | 46 | | | | | TB0096D | A005 | 2 | | 050-099, 150-199, 275-278 |
| 015 | 22 | | PA | 15-1 | 49-61-11 | D01394 | | 15 | | | | | D04796J | 29 | | | ALL |
| 016 | 22 | | PA | 13-0 | 49-61-11 | TB0096X | | A009 | BJ | | | | D01394 | 16 | | | ALL |
| 017 | 22 | | PA | 15-1 | 49-61-11 | D01394 | | 17 | | | | | D04796J | 26 | | | ALL |
| 018 | 22 | | PA | 13-0 | 49-61-11 | D01394 | | 18 | | | | | TB0096X | B009 | BJ | | ALL |
| 019 | 22 | | PA | 15-1 | 49-61-11 | D01394 | | 19 | | | | | D04796J | 25 | | | ALL |
| 021 | 22 | | PA | 13-0 | 49-61-11 | TB0096Y | | A011 | BJ | | | | D01394 | 21 | | | ALL |
| 022 | 24 | | PK | 8-1 | 36-11-41 | D01394 | | 22 | | | | | TB0064D | C010 | 2 | | ALL |
| 023 | 24 | | PK | 8-4 | 36-11-41 | D01394 | | 23 | | | | | TB0066X | C001 | BJ | | ALL |
| 025 | 24 | | PK | 4-3 | 49-72-11 | TB0096X | | D004 | BJ | | | | N00109 | - | D | | 050-099, 162-199, 275-299 |
| 025 | 24 | | PK | 14-3 | 49-72-11 | D01394 | | 25 | | | | | N00109 | - | D | | 150-157 |
| 026 | 24 | | PK | 13-0 | 49-72-11 | D01394 | | 26 | | | | | TB0096X | B004 | BJ | | ALL |
| 027 | 22 | | PA | 15-1 | 49-61-11 | D01394 | | 27 | | | | | D04796J | 27 | | | ALL |
| 032 | 24 | | PK | 4-3 | 49-72-11 | TB0096X | | A004 | BJ | | | | N00109 | + | D | | ALL |
| 042 | 20 | | PA | 6-6 | 24-27-41 | D01370 | | 2 | | | | | GD00110 | D.. | 2 | | ALL |
| 046 | 20 | | PA | 14-4 | 24-22-41 | D01370 | | 6 | | | | | D04796J | 9 | | | ALL |
| 048 | 20 | | PA | 14-4 | 24-22-41 | D01370 | | 8 | | | | | D04796J | 10 | | | ALL |
| 053 | 24 | | PK | 12-2 | 24-22-41 | D01370 | | 13 | | | | | TB0096X | A001 | BJ | | ALL |
| 054 | 24 | | PK | 12-2 | 24-22-41 | D01370 | | 14 | | | | | TB0096X | B010 | BJ | | ALL |
| 060 | 24 | | PK | 14-4 | 24-22-41 | D01370 | | 20 | | | | | D04796J | 1 | | | ALL |
| 101 | 20 | | PA | 5-1 | 24-22-41 | TB0096X | | A010 | BJ | | | | D04796J | 8 | | | ALL |
| 102 | 24 | | PK | 5-1 | 24-22-41 | TB0096X | | C010 | BJ | | | | D04796J | 2 | | | ALL |
| 103 | 24 | | PK | 5-1 | 24-22-41 | TB0096X | | A002 | BJ | | | | D04796J | 36 | | | ALL |
| 104 | 24 | | PK | 5-1 | 24-22-41 | TB0096D | | C005 | 2 | | | | D04796J | 43 | | | ALL |
| 105 | 24 | | PK | 14-4 | 24-27-41 | D01370 | | 10 | | | | | TB0096D | A005 | 2 | | ALL |
| 106 | 24 | | PK | 14-4 | 24-27-41 | D01370 | | 1 | | | | | D04796J | 47 | | | ALL |
| 107 | 24 | | PK | 5-1 | 24-41-11 | D04796J | | 45 | | | | | TB0096X | D010 | BJ | | ALL |
| 108 | 24 | | PK | 5-1 | 24-41-11 | D04796J | | 44 | | | | | TB0096X | C001 | BJ | | ALL |
| 109 | 24 | | PK | 5-1 | 24-41-11 | D04796J | | 11 | | | | | TB0096X | D001 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 1

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0060 | 286T0060 | | | P5 & P61-A2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 110 | 20 | PQ | | EJ | 5-1 | 24-41-11 | D04796J | | 12 | | | | TB0096X | D002 | BJ | | ALL |
| 110Z | | | | EJ | 0-0 | 24-41-11 | D04796J | | DED | | | | TB0096X | DED | | | ALL |
| 111 | 20 | PQ | | EK | 5-1 | 24-41-11 | D04796J | | 13 | | | | TB0096X | D009 | BJ | | ALL |
| 111Z | | | | EK | 0-0 | 24-41-11 | D04796J | | DED | | | | TB0096X | DED | | | ALL |
| 112 | 24 | PK | | | 5-1 | 24-41-12 | D04796J | | 21 | | | | TB0096X | C002 | BJ | | ALL |
| 113 | 22 | PA | | | 5-1 | 49-61-11 | TB0096Y | | A011 | BJ | | | D04796J | 28 | | | ALL |
| 114 | 20 | PA | | | 5-1 | 24-32-41 | D04796J | | 22 | | | | TB0096X | C004 | BJ | | 275-299 |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL | | | | | | | | | | | | | |
| 001 | 18 | PA | | | 5-0 | 33-13-16 | D00548 | | 9 | DK | | | D01312 | 1 | DK | | 050-099 |
| 001 | 18 | PA | | | 5-1 | 33-13-16 | D00548 | | 9 | DK | | | D01312 | 1 | DK | | 150-199, 275-277, 280-299 |
| 001 | 18 | PA | | | 3-1 | 33-13-16 | D00548 | | 9 | DK | | | D01312 | 1 | DK | | 278 |
| 002 | 18 | PA | | | 7-0 | 33-13-16 | GD00100 | | A.. | 2 | | | D01312 | 2 | DK | | 050-099, 150-199, 275-277, 280-299 |
| 002 | 18 | PA | | | 6-9 | 33-13-16 | GD00100 | | A.. | 2 | | | D01312 | 2 | DK | | 278 |
| 003 | 22 | PA | | | 9-0 | 33-16-17 | TB0070Z | | 29 | BJ | | | D01312 | 3 | | | 050-099, 150-199, 275-277, 280-299 |
| 003 | 22 | PA | | | 7-6 | 33-16-17 | TB0070Z | | 29 | BJ | | | D01312 | 3 | | | 278 |
| 004 | 22 | PA | | | 9-0 | 33-16-17 | TB0070Z | | 30 | BJ | | | D01312 | 4 | | | 050-099, 150-199, 275-277, 280-299 |
| 004 | 22 | PA | | | 7-6 | 33-16-17 | TB0070Z | | 30 | BJ | | | D01312 | 4 | | | 278 |
| 005 | 22 | PA | | | 5-0 | 29-21-32 | TB0100Y | | C030 | BJ | | | D04990J | 22 | | | 050-099, 150-199, 275-277, 280-299 |
| 005 | 22 | PA | | | 4-7 | 29-21-32 | TB0100Y | | C030 | BJ | | | D04990J | 22 | | | 278 |
| 006 | 22 | PQ | TH | | 16-0 | 29-32-11 | D01312 | | 6 | | | | TB0100Y | A029 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 006 | 22 | PQ | TH | | 12-7 | 29-32-11 | D01312 | | 6 | | | | TB0100Y | A029 | BJ | | 278 |
| 006Z | | | | | 0-0 | 29-32-11 | D01312 | | DED | | | | TB0100Y | DED | | | ALL |
| 008 | 24 | PK | | | 8-0 | 29-11-22 | D01312 | | 8 | | | | D05000P | 11 | | | 050-099, 150-199, 275-277, 280-299 |
| 008 | 24 | PK | | | 7-3 | 29-11-22 | D01312 | | 8 | | | | D05000P | 11 | | | 278 |
| 009 | 22 | PA | | | 14-0 | 29-11-22 | D01312 | | 9 | | | | D05402J | 6 | | | 050-099, 150-199, 275-277, 280-299 |
| 009 | 22 | PA | | | 12-8 | 29-11-22 | D01312 | | 9 | | | | D05402J | 6 | | | 278 |
| 010 | 22 | PA | | | 13-0 | 29-11-22 | D01312 | | 10 | | | | D04708J | 18 | | | 050-099, 150-199, 275-277, 280-299 |
| 010 | 22 | PA | | | 13-1 | 29-11-22 | D01312 | | 10 | | | | D04708J | 18 | | | 278 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 2
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 011 | 22 | | PA | 13-0 | 29-11-22 | D01312 | | 11 | | | | D04708J | 19 | | | 050-099, 150-199, 275-277, 280-299 |
| 011 | 22 | | PA | 13-1 | 29-11-22 | D01312 | | 11 | | | | D04708J | 19 | | | 278 |
| 012 | 24 | | PK | 13-0 | 29-11-22 | D01312 | | 12 | | | | D04708J | 21 | | | 050-099, 150-199, 275-277, 280-299 |
| 012 | 24 | | PK | 13-1 | 29-11-22 | D01312 | | 12 | | | | D04708J | 21 | | | 278 |
| 014 | 24 | | PK | 13-0 | 29-11-22 | D01312 | | 14 | | | | D04708J | 17 | | | 050-099, 150-199, 275-277, 280-299 |
| 014 | 24 | | PK | 13-1 | 29-11-22 | D01312 | | 14 | | | | D04708J | 17 | | | 278 |
| 015 | 22 | | PQ | TG | 16-0 | 29-32-11 | D01312 | | 15 | | | TB0100Y | C029 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 015 | 22 | | PQ | TG | 12-7 | 29-32-11 | D01312 | | 15 | | | TB0100Y | C029 | BJ | | 278 |
| 015Z | | | | TG | 0-0 | 29-32-11 | D01312 | | DED | | | TB0100Y | DED | | | ALL |
| 016 | 22 | | PQ | AP | 7-0 | 29-11-31 | D01312 | | 16 | | | TB0070Y | A015 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 016 | 22 | | PQ | AP | 7-6 | 29-11-31 | D01312 | | 16 | | | TB0070Y | A015 | BJ | | 278 |
| 016Z | | | | AP | 0-0 | 29-11-31 | D01312 | | DED | | | TB0070Y | DED | | | ALL |
| 017 | 22 | | PQ | AQ | 13-0 | 29-11-31 | D01312 | | 17 | | | TB0100Y | A031 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 017 | 22 | | PQ | AQ | 12-7 | 29-11-31 | D01312 | | 17 | | | TB0100Y | A031 | BJ | | 278 |
| 017Z | | | | AQ | 0-0 | 29-11-31 | D01312 | | DED | | | TB0100Y | DED | | | ALL |
| 018 | 22 | | PA | | 16-0 | 29-11-31 | D01312 | | 18 | | | TB0100Y | C030 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 018 | 22 | | PA | | 12-7 | 29-11-31 | D01312 | | 18 | | | TB0100Y | C030 | BJ | | 278 |
| 019 | 22 | | PA | | 5-0 | 33-16-26 | D05282J | | 22 | | | TB0098Z | 38 | BJ | | 050-099 |
| 019 | 22 | | PA | | 6-0 | 33-16-26 | D05282J | | 22 | | | TB0098Z | 38 | BJ | | 150-199, 275-277, 280-299 |
| 019 | 22 | | PA | | 4-6 | 33-16-26 | D05282J | | 22 | | | TB0098Z | 38 | BJ | | 278 |
| 01A | 18 | | PA | | 7-0 | 33-13-16 | D03896 | | 1 | DK | | D00550 | 8 | DK | | 050-099, 150-199, 275-277, 280-299 |
| 01A | 18 | | PA | | 8-2 | 33-13-16 | D03896 | | 1 | DK | | D00550 | 8 | DK | | 278 |
| 01B | 18 | | PA | | 9-0 | 33-13-16 | D03896 | | 2 | DK | | GD00086 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 01B | 18 | | PA | | 7-1 | 33-13-16 | D03896 | | 2 | DK | | GD00086 | A.. | 2 | | 278 |
| 01H | 20 | | PA | | 7-0 | 28-43-11 | D03896 | | 8 | | | GD00102 | S.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 01H | 20 | | PA | | 6-9 | 28-43-11 | D03896 | | 8 | | | GD00102 | S.. | 2 | | 278 |
| 01J | 24 | | PK | | 13-0 | 28-43-11 | D03896 | | 9 | | | D07966J | 13 | | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 3

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|--------|------|------|---------|-------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 01J | 24 | | PK | 11-11 | 28-43-11 | D03896 | | 9 | | D07966J | | 13 | | | 278 |
| 01K | 20 | | PA | 7-0 | 28-43-11 | D03896 | | 10 | | GD00102 | | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 01K | 20 | | PA | 6-9 | 28-43-11 | D03896 | | 10 | | GD00102 | | D.. | 2 | | 278 |
| 01L | 24 | | PK | 13-0 | 28-43-11 | D03896 | | 11 | | TB0100X | | C006 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 01L | 24 | | PK | 12-6 | 28-43-11 | D03896 | | 11 | | TB0100X | | C006 | BJ | | 278 |
| 020 | 22 | | PA | 13-0 | 29-11-22 | D01312 | | 20 | | D04708J | | 20 | | | 050-099, 150-199, 275-277, 280-299 |
| 020 | 22 | | PA | 13-1 | 29-11-22 | D01312 | | 20 | | D04708J | | 20 | | | 278 |
| 021 | 22 | | PA | 5-0 | 33-16-26 | D05282J | | 21 | | TB0098Z | | 37 | BJ | | 050-099 |
| 021 | 22 | | PA | 6-0 | 33-16-26 | D05282J | | 21 | | TB0098Z | | 37 | BJ | | 150-199, 275-277, 280-299 |
| 021 | 22 | | PA | 4-6 | 33-16-26 | D05282J | | 21 | | TB0098Z | | 37 | BJ | | 278 |
| 022 | 24 | | PK | 15-0 | 24-51-71 | D01312 | | 22 | | TB0102Y | | C016 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 022 | 24 | | PK | 12-8 | 24-51-71 | D01312 | | 22 | | TB0102Y | | C016 | BJ | | 278 |
| 023 | 24 | | PK | 16-0 | 24-51-71 | D01312 | | 23 | | TB0100Y | | C016 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 023 | 24 | | PK | 12-7 | 24-51-71 | D01312 | | 23 | | TB0100Y | | C016 | BJ | | 278 |
| 024 | 22 | | PA | 12-0 | 29-33-11 | D01312 | | 24 | | TB0100Y | | C025 | BJ | | 050-099 |
| 024 | 22 | | PA | 16-0 | 29-33-11 | D01312 | | 24 | | TB0100Y | | C025 | BJ | | 150-199, 275-277, 280-299 |
| 024 | 22 | | PA | 12-7 | 29-33-11 | D01312 | | 24 | | TB0100Y | | C025 | BJ | | 278 |
| 025 | 24 | | PK | 4-0 | 21-45-21 | D04708J | | 55 | | D07960J | | 28 | | | 050-099, 150-199, 275-277, 280-299 |
| 025 | 24 | | PK | 3-6 | 21-45-21 | D04708J | | 55 | | D07960J | | 28 | | | 278 |
| 026 | 22 | | PA | 5-0 | 21-45-21 | D04708J | | 56 | | D05180J | | 22 | | | 050-099, 150-156, 162-166, 275-276 |
| 026 | 20 | | PA | 5-0 | 21-45-21 | D04708J | | 56 | | D05180J | | 22 | | | 157, 167-199, 277, 280-299 |
| 026 | 20 | | PA | 3-9 | 21-45-21 | D04708J | | 56 | | D05180J | | 22 | | | 278 |
| 027 | 22 | | PA | 5-0 | 21-45-21 | D04708J | | 57 | | D05180J | | 24 | | | 050-099, 150-156, 162-166, 275-276 |
| 027 | 20 | | PA | 5-0 | 21-45-21 | D04708J | | 57 | | D05180J | | 24 | | | 157, 167-199, 277, 280-299 |
| 027 | 20 | | PA | 3-9 | 21-45-21 | D04708J | | 57 | | D05180J | | 24 | | | 278 |
| 036 | 22 | | PQ | BK | 14-0 | 29-11-22 | D03904 | 6 | | D04710J | | 37 | | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 4
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 036 | 22 | PQ | BK | 13-7 | 29-11-22 | D03904 | | 6 | | | D04710J | 37 | | | 278 | |
| 036Z | | | BK | 0-0 | 29-11-22 | D03904 | | DED | | | D04710J | DED | | | ALL | |
| 037 | 22 | PA | | 13-0 | 29-32-11 | D03904 | | 7 | | | D05652J | 1 | | | 050-099, 150-199, 275-277, 280-299 | |
| 037 | 22 | PA | | 13-5 | 29-32-11 | D03904 | | 7 | | | D05652J | 1 | | | 278 | |
| 038 | 22 | PA | | 13-0 | 29-11-11 | D03904 | | 8 | | | TB0098Y | C013 | BJ | | 050-099, 150-199, 275-277, 280-299 | |
| 038 | 22 | PA | | 12-8 | 29-11-11 | D03904 | | 8 | | | TB0098Y | C013 | BJ | | 278 | |
| 039 | 22 | PA | | 13-0 | 29-11-11 | D03904 | | 9 | | | TB0098Y | A013 | BJ | | 050-099, 150-199, 275-277, 280-299 | |
| 039 | 22 | PA | | 12-8 | 29-11-11 | D03904 | | 9 | | | TB0098Y | A013 | BJ | | 278 | |
| 03A | 20 | PA | | 8-0 | 33-13-16 | D01358 | | 1 | | | TB0064G | 8 | 2 | | 050-099, 150-199, 275-277, 280-299 | |
| 03A | 20 | PA | | 7-3 | 33-13-16 | D01358 | | 1 | | | TB0064G | 8 | 2 | | 278 | |
| 03B | 20 | PA | | 8-0 | 33-13-16 | D01358 | | 2 | | | GD00086 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 | |
| 03B | 20 | PA | | 6-9 | 33-13-16 | D01358 | | 2 | | | GD00086 | A.. | 2 | | 278 | |
| 03C | 24 | PK | | 8-0 | 21-65-11 | D01358 | | 3 | | | D05000P | 8 | | | 050-099, 150-199, 275-277, 280-299 | |
| 03C | 24 | PK | | 6-9 | 21-65-11 | D01358 | | 3 | | | D05000P | 8 | | | 278 | |
| 03D | 20 | PA | | 7-0 | 21-65-11 | D01358 | | 4 | | | GD00086 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 | |
| 03D | 20 | PA | | 6-9 | 21-65-11 | D01358 | | 4 | | | GD00086 | D.. | 2 | | 278 | |
| 03L | 20 | PA | | 7-0 | 21-65-11 | D01358 | | 11 | | | GD00086 | S.. | 2 | | 050-099, 150-199, 275-277, 280-299 | |
| 03L | 20 | PA | | 6-9 | 21-65-11 | D01358 | | 11 | | | GD00086 | S.. | 2 | | 278 | |
| 041 | 18 | PA | | 8-0 | 33-13-16 | D01324 | | 1 | DK | | TB0064G | 5 | 2 | | 050-099, 150-199, 275-277, 280-299 | |
| 041 | 18 | PA | | 7-9 | 33-13-16 | D01324 | | 1 | DK | | TB0064G | 5 | 2 | | 278 | |
| 042 | 18 | PA | | 8-0 | 33-13-16 | D01324 | | 2 | DK | | GD00086 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 | |
| 042 | 18 | PA | | 7-3 | 33-13-16 | D01324 | | 2 | DK | | GD00086 | A.. | 2 | | 278 | |
| 043 | 22 | PQ | BR | 8-0 | 33-16-17 | TB0068G | | 8 | 2 | | D01324 | 3 | | | 050-099, 150-199, 275-277, 280-299 | |
| 043 | 22 | PQ | BR | 7-7 | 33-16-17 | TB0068G | | 8 | 2 | | D01324 | 3 | | | 278 | |
| 043Z | | | BR | 0-0 | 33-16-17 | TB0068G | | DED | | | D01324 | DED | | | ALL | |
| 044 | 22 | PQ | BS | 8-0 | 33-16-17 | TB0068Z | | 15 | BJ | | D01324 | 4 | | | 050-099, 150-199, 275-277, 280-299 | |
| 044 | 22 | PQ | BS | 7-7 | 33-16-17 | TB0068Z | | 15 | BJ | | D01324 | 4 | | | 278 | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 5

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 044Z | | | | BS | 0-0 | 33-16-17 | TB0068Z | DED | | | D01324 | DED | | | ALL |
| 045 | 20 | | PA | | 8-0 | 21-31-21 | D01324 | 5 | | | GD00084 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 045 | 20 | | PA | | 7-1 | 21-31-21 | D01324 | 5 | | | GD00084 | D.. | 2 | | 278 |
| 047 | 24 | | PK | | 13-0 | 21-31-11 | D01324 | 7 | | | D05186J | 29 | | | 050-099, 150-199, 275-277, 280-299 |
| 047 | 24 | | PK | | 13-2 | 21-31-11 | D01324 | 7 | | | D05186J | 29 | | | 278 |
| 049 | 20 | | UA | | 8-0 | 21-31-11 | D01324 | | | FQ | GD00084 | S.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 049 | 20 | | UA | | 7-1 | 21-31-11 | D01324 | | | FQ | GD00084 | S.. | 2 | | 278 |
| 04C | 22 | | PA | | 6-0 | 29-21-32 | D05732J | 4 | | | D10732 | 12 | | | 050-099, 150-199, 275-277, 280-299 |
| 04C | 22 | | PA | | 4-9 | 29-21-32 | D05732J | 4 | | | D10732 | 12 | | | 278 |
| 04D | 22 | | PA | | 6-0 | 29-21-32 | TB0100Y | C031 | BJ | | D04990J | 18 | | | 050-099, 150-199, 275-277, 280-299 |
| 04D | 22 | | PA | | 4-7 | 29-21-32 | TB0100Y | C031 | BJ | | D04990J | 18 | | | 278 |
| 04E | 22 | | PA | | 6-0 | 29-21-32 | D05732J | 6 | | | D10732 | 5 | | | 050-099, 150-199, 275-277, 280-299 |
| 04E | 22 | | PA | | 4-9 | 29-21-32 | D05732J | 6 | | | D10732 | 5 | | | 278 |
| 04F | 22 | | PA | | 6-0 | 29-21-32 | TB0100Y | A031 | BJ | | D04990J | 20 | | | 050-099, 150-199, 275-277, 280-299 |
| 04F | 22 | | PA | | 4-7 | 29-21-32 | TB0100Y | A031 | BJ | | D04990J | 20 | | | 278 |
| 04G | 22 | | PA | | 4-0 | 29-21-32 | D05402J | 2 | | | TB0100Y | A030 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 04G | 22 | | PA | | 3-10 | 29-21-32 | D05402J | 2 | | | TB0100Y | A030 | BJ | | 278 |
| 04K | 22 | | PA | | 5-0 | 29-33-11 | D05732J | 11 | | | TB0098Y | C011 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 04K | 22 | | PA | | 4-2 | 29-33-11 | D05732J | 11 | | | TB0098Y | C011 | BJ | | 278 |
| 050 | 20 | | UA | | 8-0 | 21-31-21 | D01324 | | | FR | GD00084 | S.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 050 | 20 | | UA | | 7-1 | 21-31-21 | D01324 | | | FR | GD00084 | S.. | 2 | | 278 |
| 051 | 24 | | PK | | 13-0 | 21-31-11 | D01324 | 31 | | | D05400J | 3 | | | 050-099, 150-199, 275-277, 280-299 |
| 051 | 24 | | PK | | 12-7 | 21-31-11 | D01324 | 31 | | | D05400J | 3 | | | 278 |
| 052 | 24 | | PK | | 14-0 | 21-31-21 | D01324 | 12 | | | D04710J | 38 | | | 050-099, 150-199, 275-277, 280-299 |
| 052 | 24 | | PK | | 13-7 | 21-31-21 | D01324 | 12 | | | D04710J | 38 | | | 278 |
| 053 | 22 | | PA | | 5-0 | 32-45-11 | D07966J | 2 | | | D04714J | 17 | | | 050-099, 150-199, 277, 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 6
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 053 | 24 | | PK | 5-0 | 32-45-11 | D07966J | | 2 | | | D04714J | | 17 | | 275-276 |
| 053 | 22 | | PA | 3-7 | 32-45-11 | D07966J | | 2 | | | D04714J | | 17 | | 278 |
| 054 | 20 | | PA | 8-0 | 21-31-11 | D01324 | | 14 | | | GD00084 | S.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 054 | 20 | | PA | 7-1 | 21-31-11 | D01324 | | 14 | | | GD00084 | S.. | 2 | | 278 |
| 055 | 20 | | PA | 13-0 | 21-31-21 | D01324 | | 15 | | | TB0100Y | A016 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 055 | 20 | | PA | 12-7 | 21-31-21 | D01324 | | 15 | | | TB0100Y | A016 | BJ | | 278 |
| 056 | 20 | | PA | 13-0 | 21-31-11 | D01324 | | 16 | | | TB0100Y | A039 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 056 | 20 | | PA | 12-7 | 21-31-11 | D01324 | | 16 | | | TB0100Y | A039 | BJ | | 278 |
| 057 | 20 | | PQ | CG | 8-0 | 21-31-11 | D01324 | | 17 | | TB0068X | A012 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 057 | 20 | | PQ | CG | 7-7 | 21-31-11 | D01324 | | 17 | | TB0068X | A012 | BJ | | 278 |
| 057Z | | | CG | 0-0 | 21-31-11 | D01324 | | DED | | | TB0068X | DED | | | ALL |
| 058 | 24 | | PK | 5-0 | 21-61-51 | D07960J | | 13 | | | D04644J | | 9 | | 050-099, 150-199, 275-277, 280-299 |
| 058 | 24 | | PK | 3-5 | 21-61-51 | D07960J | | 13 | | | D04644J | | 9 | | 278 |
| 059 | 24 | | PK | 13-0 | 21-31-11 | D01324 | | 19 | | | D05186J | | 31 | | 050-099, 150-199, 275-277, 280-299 |
| 059 | 24 | | PK | 13-2 | 21-31-11 | D01324 | | 19 | | | D05186J | | 31 | | 278 |
| 05C | 22 | | PQ | TR | 7-0 | 33-16-17 | TB0066Y | A031 | BJ | | D01678 | | 3 | | 050-099, 150-199, 275-277, 280-299 |
| 05C | 22 | | PQ | TR | 6-9 | 33-16-17 | TB0066Y | A031 | BJ | | D01678 | | 3 | | 278 |
| 05CZ | | | TR | 0-0 | 33-16-17 | TB0066Y | | DED | | | D01678 | DED | | | ALL |
| 05D | 22 | | PQ | TQ | 8-0 | 33-16-17 | TB0066Z | | 34 | BJ | D01678 | | 4 | | 050-099, 150-199, 275-277, 280-299 |
| 05D | 22 | | PQ | TQ | 6-9 | 33-16-17 | TB0066Z | | 34 | BJ | D01678 | | 4 | | 278 |
| 05DZ | | | TQ | 0-0 | 33-16-17 | TB0066Z | | DED | | | D01678 | DED | | | ALL |
| 05E | 22 | | PA | 14-0 | 52-71-11 | D01678 | | 5 | | | D04726J | | 38 | | 050-099, 150-199, 275-277, 280-299 |
| 05E | 22 | | PA | 12-3 | 52-71-11 | D01678 | | 5 | | | D04726J | | 38 | | 278 |
| 05F | 22 | | PA | 14-0 | 52-71-12 | D01678 | | 6 | | | D04726J | | 39 | | 050-099, 150-199, 275-277, 280-299 |
| 05F | 22 | | PA | 12-3 | 52-71-12 | D01678 | | 6 | | | D04726J | | 39 | | 278 |
| 05G | 22 | | PA | 14-0 | 52-71-13 | D01678 | | 7 | | | D04726J | | 40 | | 050-099, 150-199, 275-277, 280-299 |
| 05G | 22 | | PA | 12-3 | 52-71-13 | D01678 | | 7 | | | D04726J | | 40 | | 278 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 7

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|--------|------|------|---------|---------|------|------|--|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 05H | 22 | | PA | 14-0 | 52-71-14 | D01678 | | 8 | | D04726J | | 35 | | 050-099, 150-199, 275-277, 280-299 278 | |
| 05H | 22 | | PA | 12-3 | 52-71-14 | D01678 | | 8 | | D04726J | | 35 | | 278 | |
| 05J | 22 | | PA | 14-0 | 30-31-21 | D01678 | | 9 | | D05726J | | 43 | | 050-099, 150-199, 275-277, 280-299 278 | |
| 05J | 22 | | PA | 11-11 | 30-31-21 | D01678 | | 9 | | D05726J | | 43 | | 278 | |
| 05K | 22 | | PA | 12-0 | 30-32-21 | D01678 | | 10 | | D04708J | | 2 | | 050-099, 150-199, 275-277, 280-299 278 | |
| 05K | 22 | | PA | 12-1 | 30-32-21 | D01678 | | 10 | | D04708J | | 2 | | 278 | |
| 05L | 22 | | PA | 14-0 | 30-31-23 | D01678 | | 11 | | D05726J | | 44 | | 050-099, 150-199, 275-277, 280-299 278 | |
| 05L | 22 | | PA | 11-11 | 30-31-23 | D01678 | | 11 | | D05726J | | 44 | | 278 | |
| 05M | 22 | | PQ | RI | 12-0 | SPARE | D01678 | | 12 | | D04718J | | 9 | 150-199 | |
| 05MZ | | | | RI | 0-0 | SPARE | D01678 | DED | | | D04718J | DED | | 150-199 | |
| 05N | 22 | | PQ | TJ | 8-0 | 27-61-12 | D01678 | | 13 | | TB0066X | C008 | BJ | 050-099, 150-199, 275-277, 280-299 278 | |
| 05N | 22 | | PQ | TJ | 6-9 | 27-61-12 | D01678 | | 13 | | TB0066X | C008 | BJ | 278 | |
| 05NZ | | | | TJ | 0-0 | 27-61-12 | D01678 | DED | | | TB0066X | DED | | ALL | |
| 05P | 22 | | PA | 14-0 | 27-62-11 | D01678 | | 14 | | D04714J | | 10 | | 050-099, 150-199, 275-277, 280-299 278 | |
| 05P | 22 | | PA | 12-4 | 27-62-11 | D01678 | | 14 | | D04714J | | 10 | | 278 | |
| 05S | 22 | | PA | 5-0 | 29-11-31 | D04708J | | 16 | | TB0100Y | C030 | BJ | | 050-099, 150-199, 275-277, 280-299 278 | |
| 05S | 22 | | PA | 4-3 | 29-11-31 | D04708J | | 16 | | TB0100Y | C030 | BJ | | 278 | |
| 05T | 22 | | PA | 5-0 | 29-11-31 | D05402J | | 7 | | TB0100Y | C030 | BJ | | 050-099, 150-199, 275-277, 280-299 278 | |
| 05T | 22 | | PA | 3-10 | 29-11-31 | D05402J | | 7 | | TB0100Y | C030 | BJ | | 278 | |
| 060 | 24 | | PK | 13-0 | 21-31-11 | D01324 | | 30 | | D05186J | | 30 | | 050-099, 150-199, 275-277, 280-299 278 | |
| 060 | 24 | | PK | 13-2 | 21-31-11 | D01324 | | 30 | | D05186J | | 30 | | 278 | |
| 064 | 24 | | PK | 14-0 | 21-31-21 | D01324 | | 24 | | D04710J | | 39 | | 050-099, 150-199, 275-277, 280-299 278 | |
| 064 | 24 | | PK | 13-7 | 21-31-21 | D01324 | | 24 | | D04710J | | 39 | | 278 | |
| 065 | 24 | | PK | 13-0 | 21-31-21 | D01324 | | 25 | | D05402J | | 3 | | 050-099, 150-199, 275-277, 280-299 278 | |
| 065 | 24 | | PK | 12-8 | 21-31-21 | D01324 | | 25 | | D05402J | | 3 | | 278 | |
| 066 | 22 | | PQ | FD | 8-0 | 33-16-17 | D01316 | | 40 | | TB0068Y | A019 | BJ | 050-099, 150-199, 275-277, 280-299 278 | |
| 066 | 22 | | PQ | FD | 7-10 | 33-16-17 | D01316 | | 40 | | TB0068Y | A019 | BJ | 278 | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 8

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | | |
| 066Z | | | | FD | 0-0 | 33-16-17 | D01316 | | DED | | | | | TB0068Y | DED | | | ALL |
| 067 | 22 | | PA | | 8-0 | 33-16-17 | D01316 | | 41 | | | | | TB0068Z | 22 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 067 | 22 | | PA | | 7-10 | 33-16-17 | D01316 | | 41 | | | | | TB0068Z | 22 | BJ | | 278 |
| 068 | 20 | | PA | | 8-0 | 21-31-21 | D01324 | | 28 | | | | | TB0066X | C005 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 068 | 20 | | PA | | 7-10 | 21-31-21 | D01324 | | 28 | | | | | TB0066X | C005 | BJ | | 278 |
| 069 | 20 | | PA | | 8-0 | 21-31-11 | D01324 | | 29 | | | | | D05000P | 1 | | | 050-099, 150-199, 275-277, 280-299 |
| 069 | 20 | | PA | | 7-3 | 21-31-11 | D01324 | | 29 | | | | | D05000P | 1 | | | 278 |
| 06J | 22 | | PA | | 8-0 | 30-31-13 | D05934P | | 13 | | | | | D04714J | 58 | | | ALL |
| 06K | 22 | | PA | | 7-0 | 30-31-13 | D05934P | | 14 | | | | | D05726J | 55 | | | 050-099, 150-199, 275-277, 280-299 |
| 06K | 22 | | PA | | 6-8 | 30-31-13 | D05934P | | 14 | | | | | D05726J | 55 | | | 278 |
| 071 | 24 | | PK | | 13-0 | 36-11-11 | D01316 | | 1 | | | | | D05726J | 24 | | | 050-099, 150-199, 275-277, 280-299 |
| 071 | 24 | | PK | | 13-3 | 36-11-11 | D01316 | | 1 | | | | | D05726J | 24 | | | 278 |
| 072 | 24 | | PK | | 12-0 | 36-11-11 | D01316 | | 2 | | | | | D07962J | 1 | | | 050-099, 150-199, 275-277, 280-299 |
| 072 | 24 | | PK | | 12-2 | 36-11-11 | D01316 | | 2 | | | | | D07962J | 1 | | | 278 |
| 073 | 22 | | PA | | 8-0 | 33-16-17 | TB0070Z | | 29 | BJ | | | | D01316 | 3 | | | 050-099, 150-199, 275-277, 280-299 |
| 073 | 22 | | PA | | 7-10 | 33-16-17 | TB0070Z | | 29 | BJ | | | | D01316 | 3 | | | 278 |
| 074 | 22 | | PA | | 8-0 | 33-16-17 | TB0070Z | | 30 | BJ | | | | D01316 | 4 | | | 050-099, 150-199, 275-277, 280-299 |
| 074 | 22 | | PA | | 7-10 | 33-16-17 | TB0070Z | | 30 | BJ | | | | D01316 | 4 | | | 278 |
| 075 | 24 | | PK | | 13-0 | 36-11-11 | D01316 | | 5 | | | | | D05726J | 25 | | | 050-099, 150-199, 275-277, 280-299 |
| 075 | 24 | | PK | | 13-3 | 36-11-11 | D01316 | | 5 | | | | | D05726J | 25 | | | 278 |
| 076 | 22 | | PA | | 13-0 | 36-11-11 | D01316 | | 6 | | | | | D05726J | 26 | | | 050-099, 150-199, 275-277, 280-299 |
| 076 | 22 | | PA | | 13-3 | 36-11-11 | D01316 | | 6 | | | | | D05726J | 26 | | | 278 |
| 079 | 24 | | PK | | 5-0 | 21-61-71 | D07960J | | 19 | | | | | D04708J | 23 | | | 050-099, 150-199, 275-277, 280-299 |
| 079 | 24 | | PK | | 3-6 | 21-61-71 | D07960J | | 19 | | | | | D04708J | 23 | | | 278 |
| 080 | 24 | | PK | | 13-0 | 36-11-51 | D01316 | | 10 | | | | | D05726J | 36 | | | 050-099, 150-199, 275-277, 280-299 |
| 080 | 24 | | PK | | 13-3 | 36-11-51 | D01316 | | 10 | | | | | D05726J | 36 | | | 278 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 9

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 081 | 24 | | PK | 13-0 | 36-11-51 | D01316 | | 11 | | TB0098X | D004 | BJ | | 050-099, 150-199, 275-277, 280-299 | |
| 081 | 24 | | PK | 12-11 | 36-11-51 | D01316 | | 11 | | TB0098X | D004 | BJ | | 278 | |
| 083 | 24 | | PK | 13-0 | 36-11-31 | D01316 | | 13 | | D05726J | 29 | | | 050-099, 150-199, 275-277, 280-299 | |
| 083 | 24 | | PK | 13-3 | 36-11-31 | D01316 | | 13 | | D05726J | 29 | | | 278 | |
| 084 | 24 | | PK | 12-0 | 36-11-31 | D01316 | | 14 | | D07962J | 3 | | | 050-099, 150-199, 275-277, 280-299 | |
| 084 | 24 | | PK | 12-2 | 36-11-31 | D01316 | | 14 | | D07962J | 3 | | | 278 | |
| 085 | 24 | | PK | 15-0 | 36-11-31 | D01316 | | 15 | | D05726J | 30 | | | 050-099, 150-199, 275-277, 280-299 | |
| 085 | 24 | | PK | 13-3 | 36-11-31 | D01316 | | 15 | | D05726J | 30 | | | 278 | |
| 087 | 22 | | PA | 13-0 | 36-11-11 | D01316 | | 17 | | D05400J | 11 | | | 050-099, 150-199, 275-277, 280-299 | |
| 087 | 22 | | PA | 12-10 | 36-11-11 | D01316 | | 17 | | D05400J | 11 | | | 278 | |
| 088 | 24 | | PK | 5-0 | 21-61-71 | D07960J | | 20 | | D04644J | 21 | | | 050-099, 150-199, 275-277, 280-299 | |
| 088 | 24 | | PK | 3-5 | 21-61-71 | D07960J | | 20 | | D04644J | 21 | | | 278 | |
| 089R | 22 | | PH | 13-0 | 26-18-31 | D04644J | | 32 | | D01316 | 19 | | | 050-099 | |
| 089R | 22 | | PH | 14-0 | 26-18-31 | D04644J | | 32 | | D01316 | 19 | | | 150-199, 275-277, 280-299 | |
| 089R | 22 | | PH | 13-4 | 26-18-31 | D04644J | | 32 | | D01316 | 19 | | | 278 | |
| 08B | 22 | | PA | 8-10 | 52-51-11 | D00874 | | 8 | | GD00265 | D.. | 2 | | 050-099, 152, 154, 156, 275-299 | |
| 08B | 22 | | PA | 4-0 | 52-51-11 | D00874 | | 8 | | GD00265 | D.. | 2 | | 150-151, 153, 155, 157-199 | |
| 090 | 24 | | PK | 5-0 | 21-61-61 | D07960J | | 16 | | D04708J | 48 | | | 050-099, 150-199, 275-277, 280-299 | |
| 090 | 24 | | PK | 3-6 | 21-61-61 | D07960J | | 16 | | D04708J | 48 | | | 278 | |
| 091 | 24 | | PK | 5-0 | 21-61-61 | D07960J | | 18 | | D04644J | 11 | | | 050-099, 150-199, 275-277, 280-299 | |
| 091 | 24 | | PK | 3-5 | 21-61-61 | D07960J | | 18 | | D04644J | 11 | | | 278 | |
| 093 | 22 | | PA | 13-0 | 36-11-51 | D01316 | | 23 | | D05726J | 35 | | | 050-099, 150-199, 275-277, 280-299 | |
| 093 | 22 | | PA | 13-3 | 36-11-51 | D01316 | | 23 | | D05726J | 35 | | | 278 | |
| 094 | 24 | | PK | 15-0 | 36-11-61 | D01316 | | 24 | | D05726J | 39 | | | 050-099, 150-199, 275-277, 280-299 | |
| 094 | 24 | | PK | 13-3 | 36-11-61 | D01316 | | 24 | | D05726J | 39 | | | 278 | |

WIRE LIST

D280T132

91-21-11
Section W0060
Page 10
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 095 | 20 | | PA | 8-0 | 36-11-61 | D01316 | | 25 | | | | | GD00084 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 095 | 20 | | PA | 7-4 | 36-11-61 | D01316 | | 25 | | | | | GD00084 | D.. | 2 | | 278 |
| 097 | 24 | | PK | 15-0 | 36-11-41 | D01316 | | 27 | | | | | D05726J | 15 | | | 050-099, 150-199, 275-277, 280-299 |
| 097 | 24 | | PK | 13-3 | 36-11-41 | D01316 | | 27 | | | | | D05726J | 15 | | | 278 |
| 098 | 24 | | PK | 15-0 | 36-11-41 | D01316 | | 28 | | | | | D05726J | 14 | | | 050-099, 150-199, 275-277, 280-299 |
| 098 | 24 | | PK | 13-3 | 36-11-41 | D01316 | | 28 | | | | | D05726J | 14 | | | 278 |
| 099 | 22 | | PA | 12-0 | 31-31-26 | D03904 | | 10 | | | | | TB0098X | A002 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 099 | 22 | | PA | 12-8 | 31-31-26 | D03904 | | 10 | | | | | TB0098X | A002 | BJ | | 278 |
| 09B | 16 | | PA | 7-0 | 33-13-16 | D00896 | | 2 | FM | | | | TB0068G | 5 | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 09B | 16 | | PA | 6-7 | 33-13-16 | D00896 | | 2 | FM | | | | TB0068G | 5 | 2 | | 278 |
| 09G | 20 | | PA | 7-0 | 33-13-16 | D00896 | | 7 | | | | | GD00084 | S.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 09G | 20 | | PA | 6-2 | 33-13-16 | D00896 | | 7 | | | | | GD00084 | S.. | 2 | | 278 |
| 09H | 16 | | PA | 7-0 | 33-13-16 | D00896 | | 8 | FM | | | | TB0068H | 3 | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 09H | 16 | | PA | 6-7 | 33-13-16 | D00896 | | 8 | FM | | | | TB0068H | 3 | 2 | | 278 |
| 09J | 16 | | PA | 7-0 | 33-13-16 | D00896 | | 9 | FM | | | | TB0068H | 1 | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 09J | 16 | | PA | 6-7 | 33-13-16 | D00896 | | 9 | FM | | | | TB0068H | 1 | 2 | | 278 |
| 09L | 16 | | PA | 7-0 | 33-13-16 | D00896 | | 11 | FM | | | | GD00084 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 09L | 16 | | PA | 6-2 | 33-13-16 | D00896 | | 11 | FM | | | | GD00084 | A.. | 2 | | 278 |
| 09M | 22 | | PA | 7-0 | 33-13-16 | D00896 | | 12 | | | | | TB0064Z | 12 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 09M | 22 | | PA | 6-10 | 33-13-16 | D00896 | | 12 | | | | | TB0064Z | 12 | BJ | | 278 |
| 100 | 24 | | PK | 14-0 | 73-21-15 | D01316 | | 30 | | | | | TB0100X | C008 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 100 | 24 | | PK | 12-10 | 73-21-15 | D01316 | | 30 | | | | | TB0100X | C008 | BJ | | 278 |
| 101 | 20 | | PQ | CF | 11-0 | 78-34-11 | TB0098X | A003 | BJ | | | | D04718J | 28 | | | 050-099, 150-199, 275-277, 280-299 |
| 101 | 20 | | PQ | CF | 4-7 | 78-34-11 | TB0098X | A003 | BJ | | | | D04718J | 28 | | | 278 |
| 101Z | | | | CF | 0-0 | 78-34-11 | TB0098X | DED | | | | | D04718J | | | GE | ALL |
| 102 | 24 | | PK | 14-0 | 73-21-15 | D01316 | | 32 | | | | | TB0098X | C008 | BJ | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 11

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 102 | 24 | | PK | 12-11 | 73-21-15 | D01316 | | 32 | | | TB0098X | C008 | BJ | | 278 |
| 103 | 22 | | PA | 4-0 | 78-36-11 | D04710J | | 3 | | | TB0102X | B010 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 103 | 22 | | PA | 4-10 | 78-36-11 | D04710J | | 3 | | | TB0102X | B010 | BJ | | 278 |
| 104 | 22 | | PA | 13-0 | 36-11-11 | D01316 | | 34 | | | D05726J | 27 | | | 050-099, 150-199, 275-277, 280-299 |
| 104 | 22 | | PA | 13-3 | 36-11-11 | D01316 | | 34 | | | D05726J | 27 | | | 278 |
| 105R | 22 | | PH | 4-0 | 26-18-21 | TB0100D | | C010 | 2 | | D04644J | 30 | | | 050-099, 150-199, 275-277, 280-299 |
| 105R | 22 | | PH | 4-3 | 26-18-21 | TB0100D | | C010 | 2 | | D04644J | 30 | | | 278 |
| 106R | 22 | | PH | 4-0 | 26-18-11 | TB0100D | | C009 | 2 | | D04644J | 28 | | | 050-099, 150-199, 275-277, 280-299 |
| 106R | 22 | | PH | 4-3 | 26-18-11 | TB0100D | | C009 | 2 | | D04644J | 28 | | | 278 |
| 107 | 24 | | PK | 5-0 | 21-58-11 | D04708J | | 42 | | | TB0102Y | A030 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 107 | 24 | | PK | 4-4 | 21-58-11 | D04708J | | 42 | | | TB0102Y | A030 | BJ | | 278 |
| 108 | 22 | | PA | 14-0 | 36-22-11 | D01316 | | 38 | | | D04710J | 5 | | | 050-099, 150-199, 275-277, 280-299 |
| 108 | 22 | | PA | 13-10 | 36-22-11 | D01316 | | 38 | | | D04710J | 5 | | | 278 |
| 109 | 20 | | PA | 8-0 | 33-13-16 | D02083 | | 1 | | | TB0068H | 6 | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 109 | 20 | | PA | 7-5 | 33-13-16 | D02083 | | 1 | | | TB0068H | 6 | 2 | | 278 |
| 10A | 22 | | PA | 6-0 | 33-13-16 | D05000P | | 9 | | | TB0064Z | 12 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 10A | 22 | | PA | 6-4 | 33-13-16 | D05000P | | 9 | | | TB0064Z | 12 | BJ | | 278 |
| 10B | 16 | | PA | 8-0 | 33-13-16 | D00898 | | 2 | FM | | TB0064G | 1 | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 10B | 16 | | PA | 8-5 | 33-13-16 | D00898 | | 2 | FM | | TB0064G | 1 | 2 | | 278 |
| 10G | 20 | | PA | 8-0 | 33-13-16 | D00898 | | 7 | | | GD00086 | S.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 10G | 20 | | PA | 7-10 | 33-13-16 | D00898 | | 7 | | | GD00086 | S.. | 2 | | 278 |
| 10J | 16 | | PA | 8-0 | 33-13-16 | D00898 | | 9 | FM | | TB0064G | 3 | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 10J | 16 | | PA | 8-5 | 33-13-16 | D00898 | | 9 | FM | | TB0064G | 3 | 2 | | 278 |
| 10L | 16 | | PA | 8-0 | 33-13-16 | D00898 | | 11 | FM | | GD00086 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 10L | 16 | | PA | 7-10 | 33-13-16 | D00898 | | 11 | FM | | GD00086 | A.. | 2 | | 278 |
| 10M | 22 | | PA | 5-0 | 33-13-16 | D10860 | | A2 | | | TB0064Z | 12 | BJ | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 12
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 10M | 22 | | PA | 6-0 | 33-13-16 | D10860 | | A2 | | | | | TB0064Z | 12 | BJ | | 150-199, 275-277, 280-299 |
| 10M | 22 | | PA | 4-9 | 33-13-16 | D10860 | | A2 | | | | | TB0064Z | 12 | BJ | | 278 |
| 10N | 24 | | PK | 8-0 | 33-13-16 | D05000P | | 17 | | | | | D10860 | X1 | | | 050-099, 150-199, 275-277, 280-299 |
| 10N | 24 | | PK | 7-8 | 33-13-16 | D05000P | | 17 | | | | | D10860 | X1 | | | 278 |
| 10P | 22 | | PA | 10-0 | 33-13-16 | D10860 | | A1 | | | | | D00898 | 12 | | | 050-099, 150-199, 275-277, 280-299 |
| 10P | 22 | | PA | 9-9 | 33-13-16 | D10860 | | A1 | | | | | D00898 | 12 | | | 278 |
| 10R | 20 | | PA | 7-0 | 33-13-16 | D10860 | | X2 | | | | | GD00100 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 10R | 20 | | PA | 7-1 | 33-13-16 | D10860 | | X2 | | | | | GD00100 | A.. | 2 | | 278 |
| 10S | 22 | | PA | 3-0 | 33-13-16 | D10860 | | B1 | | | | | D00558 | 12 | | | 050-099 |
| 10S | 22 | | PA | 7-0 | 33-13-16 | D10860 | | B1 | | | | | D00558 | 12 | | | 150-199, 275-277, 280-299 |
| 10S | 22 | | PA | 2-7 | 33-13-16 | D10860 | | B1 | | | | | D00558 | 12 | | | 278 |
| 10T | 22 | | PA | 6-0 | 33-13-16 | D10860 | | B2 | | | | | TB0064Z | 12 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 10T | 22 | | PA | 4-9 | 33-13-16 | D10860 | | B2 | | | | | TB0064Z | 12 | BJ | | 278 |
| 110 | 20 | | PA | 7-0 | 33-13-16 | D02083 | | 2 | | | | | GD00100 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 110 | 20 | | PA | 6-8 | 33-13-16 | D02083 | | 2 | | | | | GD00100 | A.. | 2 | | 278 |
| 111 | 22 | | PA | 7-0 | 33-16-17 | D02083 | | 3 | | | | | TB0068Y | C020 | BJ | | 050-099 |
| 111 | 22 | | PA | 8-0 | 33-16-17 | D02083 | | 3 | | | | | TB0068Y | C020 | BJ | | 150-199, 275-277, 280-299 |
| 111 | 22 | | PA | 7-5 | 33-16-17 | D02083 | | 3 | | | | | TB0068Y | C020 | BJ | | 278 |
| 112 | 22 | | PA | 7-0 | 33-16-17 | D02083 | | 4 | | | | | TB0068Z | 21 | BJ | | 050-099 |
| 112 | 22 | | PA | 8-0 | 33-16-17 | D02083 | | 4 | | | | | TB0068Z | 21 | BJ | | 150-199, 275-277, 280-299 |
| 112 | 22 | | PA | 7-5 | 33-16-17 | D02083 | | 4 | | | | | TB0068Z | 21 | BJ | | 278 |
| 113 | 24 | | PK | 5-0 | 21-58-11 | D04708J | | 58 | | | | | TB0102Y | C028 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 113 | 24 | | PK | 4-4 | 21-58-11 | D04708J | | 58 | | | | | TB0102Y | C028 | BJ | | 278 |
| 119 | 22 | | PA | 13-0 | 36-11-31 | D01316 | | 49 | | | | | D05726J | 31 | | | 050-099, 150-199, 275-277, 280-299 |
| 119 | 22 | | PA | 13-3 | 36-11-31 | D01316 | | 49 | | | | | D05726J | 31 | | | 278 |
| 11G | 20 | | PA | 7-0 | 33-13-16 | D00548 | | 7 | | | | | GD00100 | S.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 11G | 20 | | PA | 6-0 | 33-13-16 | D00548 | | 7 | | | | | GD00100 | S.. | 2 | | 278 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 13

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 11H | 16 | | PA | 7-0 | 33-13-16 | D00548 | | 8 | FM | | | | TB0068H | 6 | 2 | 050-099, 150-199, 275-277, 280-299 |
| 11H | 16 | | PA | 6-10 | 33-13-16 | D00548 | | 8 | FM | | | | TB0068H | 6 | 2 | 278 |
| 11L | 16 | | PA | 7-0 | 33-13-16 | D00548 | | 11 | FM | | | | GD00100 | A.. | 2 | 050-099, 150-199, 275-277, 280-299 |
| 11L | 16 | | PA | 6-0 | 33-13-16 | D00548 | | 11 | FM | | | | GD00100 | A.. | 2 | 278 |
| 11M | 22 | | PA | 7-0 | 33-13-16 | D00548 | | 12 | | | | | TB0064Z | 12 | BJ | ALL |
| 120 | 24 | | PK | 14-0 | 36-11-31 | D01316 | | 50 | | | | | D05402J | 11 | | 050-099, 150-199, 275-277, 280-299 |
| 120 | 24 | | PK | 12-11 | 36-11-31 | D01316 | | 50 | | | | | D05402J | 11 | | 278 |
| 121 | 22 | | PA | 13-0 | 36-11-31 | D01316 | | 51 | | | | | D05726J | 32 | | 050-099, 150-199, 275-277, 280-299 |
| 121 | 22 | | PA | 13-3 | 36-11-31 | D01316 | | 51 | | | | | D05726J | 32 | | 278 |
| 122 | 24 | | PK | 14-0 | 21-26-31 | D13572 | | 8 | | | | | D04726J | 26 | | 050-099, 150-199, 275-277, 280-299 |
| 122 | 24 | | PK | 13-4 | 21-26-31 | D13572 | | 8 | | | | | D04726J | 26 | | 278 |
| 123 | 24 | | PK | 5-0 | 21-26-31 | TB0098Y | | A014 | BJ | | | | D04726J | 27 | | 050-099, 150-199, 275-277, 280-299 |
| 123 | 24 | | PK | 4-6 | 21-26-31 | TB0098Y | | A014 | BJ | | | | D04726J | 27 | | 278 |
| 124 | 24 | | PK | 13-0 | 21-28-11 | D13572 | | 10 | | | | | TB0100Y | C015 | BJ | 050-099, 150-199, 275-277, 280-299 |
| 124 | 24 | | PK | 12-8 | 21-28-11 | D13572 | | 10 | | | | | TB0100Y | C015 | BJ | 278 |
| 125 | 22 | | PA | 13-0 | 36-11-61 | D01316 | | 55 | | | | | D05726J | 38 | | 050-099, 150-199, 275-277, 280-299 |
| 125 | 22 | | PA | 13-3 | 36-11-61 | D01316 | | 55 | | | | | D05726J | 38 | | 278 |
| 128 | 24 | | PK | 5-0 | 21-28-11 | D04726J | | 16 | | | | | TB0100Y | C015 | BJ | 050-099, 150-199, 275-277, 280-299 |
| 128 | 24 | | PK | 4-5 | 21-28-11 | D04726J | | 16 | | | | | TB0100Y | C015 | BJ | 278 |
| 129 | 24 | | PK | 5-0 | 21-43-11 | TB0104Y | | A014 | BJ | | | | D04726J | 29 | | 050-099, 150-199, 275-277, 280-299 |
| 129 | 24 | | PK | 4-9 | 21-43-11 | TB0104Y | | A014 | BJ | | | | D04726J | 29 | | 278 |
| 12B | 16 | | PA | 4-0 | 33-13-16 | D00550 | | 2 | FM | | | | D10402 | A2 | | 050-099, 150-199, 275-277, 280-299 |
| 12B | 16 | | PA | 3-1 | 33-13-16 | D00550 | | 2 | FM | | | | D10402 | A2 | | 278 |
| 12G | 20 | | PA | 7-0 | 33-13-16 | D00550 | | 7 | | | | | GD00086 | S.. | 2 | 050-099, 150-199, 275-277, 280-299 |
| 12G | 20 | | PA | 6-9 | 33-13-16 | D00550 | | 7 | | | | | GD00086 | S.. | 2 | 278 |
| 12J | 16 | | PA | 7-0 | 33-13-16 | D00550 | | 9 | FM | | | | TB0064G | 5 | 2 | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 14

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|------|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | | |
| 12J | 16 | | PA | | 7-4 | 33-13-16 | D00550 | | 9 | FM | | | | TB0064G | | 5 | 2 | 278 |
| 12L | 16 | | PA | | 7-0 | 33-13-16 | D00550 | | 11 | FM | | | | GD00086 | | A.. | 2 | 050-099, 150-199, 275-277, 280-299 |
| 12L | 16 | | PA | | 6-9 | 33-13-16 | D00550 | | 11 | FM | | | | GD00086 | | A.. | 2 | 278 |
| 12M | 22 | | PA | | 8-0 | 33-13-16 | TB0064G | | 5 | 2 | | | | D10402 | | B2 | | 050-099, 150-199, 275-277, 280-299 |
| 12M | 22 | | PA | | 8-1 | 33-13-16 | TB0064G | | 5 | 2 | | | | D10402 | | B2 | | 278 |
| 12P | 24 | | PK | | 9-0 | 33-13-16 | D10402 | | X1 | | | | | TB0064Y | | C019 | BJ | 050-099, 150-199, 275-277, 280-299 |
| 12P | 24 | | PK | | 8-1 | 33-13-16 | D10402 | | X1 | | | | | TB0064Y | | C019 | BJ | 278 |
| 12R | 20 | | PA | | 6-0 | 33-13-16 | D10402 | | X2 | | | | | GD00100 | | A.. | 2 | 050-099, 150-199, 275-277, 280-299 |
| 12R | 20 | | PA | | 4-6 | 33-13-16 | D10402 | | X2 | | | | | GD00100 | | A.. | 2 | 278 |
| 12S | 22 | | PA | | 8-0 | 33-13-16 | D10402 | | B1 | | | | | TB0064G | | 2 | 2 | 050-099, 150-199, 275-277, 280-299 |
| 12S | 22 | | PA | | 8-1 | 33-13-16 | D10402 | | B1 | | | | | TB0064G | | 2 | 2 | 278 |
| 12T | 22 | | PQ | RH | 7-0 | 33-13-16 | D00550 | | 12 | | | | | TB0064X | | A018 | BJ | 050-099, 150-199, 275-277, 280-299 |
| 12T | 22 | | PQ | RH | 7-4 | 33-13-16 | D00550 | | 12 | | | | | TB0064X | | A018 | BJ | 278 |
| 12TZ | | | | RH | 0-0 | 33-13-16 | D00550 | | DED | | | | | TB0064X | | DED | | ALL |
| 12V | 16 | | PA | | 9-0 | 33-13-16 | D10402 | | A1 | | | | | TB0064G | | 4 | 2 | 050-099, 150-199, 275-277, 280-299 |
| 12V | 16 | | PA | | 8-1 | 33-13-16 | D10402 | | A1 | | | | | TB0064G | | 4 | 2 | 278 |
| 12W | 24 | | PK | | 2-0 | 33-13-16 | TB0278R | | C002 | 2 | | | | TB0278R | | A001 | 2 | 050-099, 150-199, 275-277, 280-299 |
| 12W | 24 | | PK | | 0-7 | 33-13-16 | TB0278R | | C002 | 2 | | | | TB0278R | | A001 | 2 | 278 |
| 12X | 24 | | PK | | 9-0 | 33-13-16 | TB0064Y | | C019 | BJ | | | | D10404 | | X1 | | 050-099, 150-199, 275-277, 280-299 |
| 12X | 24 | | PK | | 8-1 | 33-13-16 | TB0064Y | | C019 | BJ | | | | D10404 | | X1 | | 278 |
| 12Y | 20 | | PA | | 6-0 | 33-13-16 | GD00100 | | A.. | 2 | | | | D10404 | | X2 | | 050-099, 150-199, 275-277, 280-299 |
| 12Y | 20 | | PA | | 4-5 | 33-13-16 | GD00100 | | A.. | 2 | | | | D10404 | | X2 | | 278 |
| 12Z | 24 | | PK | | 2-0 | 33-13-16 | TB0278R | | A002 | 2 | | | | D10404 | | C3 | | 050-099, 150-199, 275-277, 280-299 |
| 12Z | 24 | | PK | | 1-9 | 33-13-16 | TB0278R | | A002 | 2 | | | | D10404 | | C3 | | 278 |
| 130 | 24 | | PK | | 5-0 | 21-43-11 | TB0102Y | | C033 | BJ | | | | D04726J | | 28 | | 050-099, 150-199, 275-277, 280-299 |
| 130 | 24 | | PK | | 4-6 | 21-43-11 | TB0102Y | | C033 | BJ | | | | D04726J | | 28 | | 278 |
| 131 | 20 | | PA | | 8-0 | 33-13-16 | D03892 | | 1 | | | | | TB0068H | | 1 | 2 | 050-099, 278 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 15

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 131 | 20 | | PA | 9-0 | 33-13-16 | D03892 | | 1 | | | | | TB0068H | 1 | 2 | | 150-199, 275-277, 280-299 |
| 132 | 20 | | PA | 9-0 | 33-13-16 | D03892 | | 2 | | | | | GD00086 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 132 | 20 | | PA | 7-8 | 33-13-16 | D03892 | | 2 | | | | | GD00086 | A.. | 2 | | 278 |
| 133 | 22 | | PQ | RY | 8-0 | 33-16-17 | TB0068Y | A020 | BJ | | | | D01328 | 3 | | | 050-099, 150-199, 275-277, 280-299 |
| 133 | 22 | | PQ | RY | 7-11 | 33-16-17 | TB0068Y | A020 | BJ | | | | D01328 | 3 | | | 278 |
| 133Z | | | | RY | 0-0 | 33-16-17 | TB0068Y | DED | | | | | D01328 | DED | | | ALL |
| 134 | 22 | | PQ | RG | 8-0 | 33-16-17 | TB0068Z | 21 | BJ | | | | D01328 | 4 | | | 050-099, 150-199, 275-277, 280-299 |
| 134 | 22 | | PQ | RG | 7-11 | 33-16-17 | TB0068Z | 21 | BJ | | | | D01328 | 4 | | | 278 |
| 134Z | | | | RG | 0-0 | 33-16-17 | TB0068Z | DED | | | | | D01328 | DED | | | ALL |
| 135 | 20 | | PA | | 8-0 | 21-58-11 | D01328 | 5 | | | | | GD00084 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 135 | 20 | | PA | | 7-5 | 21-58-11 | D01328 | 5 | | | | | GD00084 | D.. | 2 | | 278 |
| 137 | 24 | | PK | | 15-0 | 21-58-11 | D01328 | 7 | | | | | D05652J | 2 | | | 050-099 |
| 137 | 24 | | PK | | 14-0 | 21-58-11 | D01328 | 7 | | | | | D05652J | 2 | | | 150-199, 275-277, 280-299 |
| 137 | 24 | | PK | | 13-9 | 21-58-11 | D01328 | 7 | | | | | D05652J | 2 | | | 278 |
| 138 | 24 | | PK | | 15-0 | 21-58-12 | D01328 | 8 | | | | | D04708J | 25 | | | 050-099 |
| 138 | 24 | | PK | | 14-0 | 21-58-12 | D01328 | 8 | | | | | D04708J | 25 | | | 150-199, 275-277, 280-299 |
| 138 | 24 | | PK | | 13-6 | 21-58-12 | D01328 | 8 | | | | | D04708J | 25 | | | 278 |
| 139 | 24 | | PK | | 14-0 | 21-58-12 | D01328 | 9 | | | | | D05652J | 3 | | | 050-099, 150-199, 275-277, 280-299 |
| 139 | 24 | | PK | | 13-9 | 21-58-12 | D01328 | 9 | | | | | D05652J | 3 | | | 278 |
| 13A | 20 | | PQ | CI | 11-0 | 78-34-21 | TB0104X | C009 | BJ | | | | D04710J | 54 | | | 050-099, 150-199, 275-277, 280-299 |
| 13A | 20 | | PQ | CI | 5-1 | 78-34-21 | TB0104X | C009 | BJ | | | | D04710J | 54 | | | 278 |
| 13AZ | | | | CI | 0-0 | 78-34-21 | TB0104X | D009 | BJ | | | | D04710J | | | GF | ALL |
| 13G | 20 | | PA | | 5-0 | 33-13-16 | D00558 | 7 | | | | | GD00086 | S.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 13G | 20 | | PA | | 3-5 | 33-13-16 | D00558 | 7 | | | | | GD00086 | S.. | 2 | | 278 |
| 13H | 16 | | PA | | 5-0 | 33-13-16 | D00558 | 8 | FM | | | | TB0064G | 8 | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 13H | 16 | | PA | | 3-11 | 33-13-16 | D00558 | 8 | FM | | | | TB0064G | 8 | 2 | | 278 |
| 13J | 16 | | PA | | 5-0 | 33-13-16 | D00558 | 9 | FM | | | | TB0064G | 7 | 2 | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 16
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 13J | 16 | | PA | 3-11 | 33-13-16 | D00558 | | 9 | FM | | | | TB0064G | 7 | 2 | 278 |
| 13L | 16 | | PA | 5-0 | 33-13-16 | D00558 | | 11 | FM | | | | GD00086 | A.. | 2 | 050-099, 150-199, 275-277, 280-299 |
| 13L | 16 | | PA | 3-5 | 33-13-16 | D00558 | | 11 | FM | | | | GD00086 | A.. | 2 | 278 |
| 142 | 22 | | PQ | RD | 13-0 | 21-33-11 | TB0100Z | | 20 | BJ | | | D01328 | 12 | | 050-099, 150-199, 275-277, 280-299 |
| 142 | 22 | | PQ | RD | 12-11 | 21-33-11 | TB0100Z | | 20 | BJ | | | D01328 | 12 | | 278 |
| 142Z | | | | RD | 0-0 | 21-33-11 | TB0100Z | | DED | | | | D01328 | DED | | ALL |
| 143 | 22 | | PQ | RE | 13-0 | 21-58-16 | D01328 | | 1 | | | | TB0106X | D010 | BJ | 050-099, 150-199, 275-277, 280-299 |
| 143 | 22 | | PQ | RE | 13-3 | 21-58-16 | D01328 | | 1 | | | | TB0106X | D010 | BJ | 278 |
| 143Z | | | | RE | 0-0 | 21-58-16 | D01328 | | DED | | | | TB0106X | DED | | ALL |
| 144 | 22 | | PQ | RF | 12-0 | 21-58-11 | D01328 | | 2 | | | | TB0098Y | A011 | BJ | 050-099, 150-199, 275-277, 280-299 |
| 144 | 22 | | PQ | RF | 13-0 | 21-58-11 | D01328 | | 2 | | | | TB0098Y | A011 | BJ | 278 |
| 144Z | | | | RF | 0-0 | 21-58-11 | D01328 | | DED | | | | TB0098Y | DED | | ALL |
| 147 | 24 | | PV | AR | 5-0 | 23-51-41 | D00551 | | 29 | | | | SM00010 | | 9 | 150-152 |
| 147Z | | | | AR | 0-0 | 23-51-41 | D00551 | | | | FZ | | D00557 | | | 150-152 |
| 149 | 24 | | PK | | 5-0 | 21-61-81 | TB0102X | | C010 | BJ | | | D04726J | 30 | | 050-099 |
| 149 | 24 | | PK | | 5-0 | 21-61-81 | D04726J | | 30 | | | | TB0102X | C010 | BJ | 150-199, 275-277, 280-299 |
| 149 | 24 | | PK | | 4-6 | 21-61-81 | D04726J | | 30 | | | | TB0102X | C010 | BJ | 278 |
| 150 | 24 | | PK | | 8-0 | 21-61-81 | D13572 | | 9 | | | | TB0070X | A004 | BJ | 050-099, 150-199, 275-277, 280-299 |
| 150 | 24 | | PK | | 7-7 | 21-61-81 | D13572 | | 9 | | | | TB0070X | A004 | BJ | 278 |
| 151 | 20 | | PA | | 8-0 | 21-61-81 | D13572 | | 7 | | | | GD00265 | D.. | 2 | 050-099, 275-277, 280-299 |
| 151 | 20 | | PA | | 7-1 | 21-61-81 | D13572 | | 7 | | | | GD00265 | D.. | 2 | 150-199 |
| 173R | 22 | | PH | | 13-0 | 26-18-11 | TB0100D | | A009 | 2 | | | D01316 | 37 | | 278 |
| 173R | 22 | | PH | | 13-0 | 26-18-11 | D01316 | | 37 | | | | SM00004 | | 9 | 050-099 |
| 173R | 22 | | PH | | 13-0 | 26-18-11 | D01316 | | 37 | | | | TB0100D | A009 | 2 | 150-157, 275-277, 280-299 |
| 173R | 22 | | PH | | 12-11 | 26-18-11 | D01316 | | 37 | | | | SM00004 | | 9 | 162-199 |
| 174R | 22 | | PH | | 2-0 | 26-18-21 | TB0100D | | A010 | 2 | | | TB0100Y | A011 | BJ | 278 |
| 174R | 22 | | PH | | 0-7 | 26-18-21 | TB0100D | | A010 | 2 | | | TB0100Y | A011 | BJ | 150-157, 275-277, 280-299 |
| 177 | 24 | | PK | | 5-0 | 21-61-81 | TB0102X | | C007 | BJ | | | D04726J | 4 | | 278 |
| | | | | | | | | | | | | | | | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 17

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 177 | 24 | | PK | | 4-6 | 21-61-81 | TB0102X | C007 | BJ | | D04726J | 4 | | | 278 |
| 179 | 24 | | PK | | 5-0 | 21-61-81 | TB0102X | D007 | BJ | | D04726J | 5 | | | 050-099, 150-199, 275-277, 280-299 |
| 179 | 24 | | PK | | 4-6 | 21-61-81 | TB0102X | D007 | BJ | | D04726J | 5 | | | 278 |
| 17J | 24 | | PK | | 7-0 | 31-41-13 | D00419 | | 9 | | TB0100Z | 21 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 17J | 24 | | PK | | 6-10 | 31-41-13 | D00419 | | 9 | | TB0100Z | 21 | BJ | | 278 |
| 17K | 24 | | PK | | 6-0 | 31-41-13 | D00419 | | 10 | | D05311J | 5 | | | 050-099, 150-199, 275-277, 280-299 |
| 17K | 24 | | PK | | 5-1 | 31-41-13 | D00419 | | 10 | | D05311J | 5 | | | 278 |
| 17L | 24 | | PK | | 7-0 | 31-41-13 | D00419 | | 11 | | TB0100Z | 21 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 17L | 24 | | PK | | 6-10 | 31-41-13 | D00419 | | 11 | | TB0100Z | 21 | BJ | | 278 |
| 17M | 24 | | PK | | 6-0 | 31-41-13 | D00419 | | 12 | | D05311J | 6 | | | 050-099, 150-199, 275-277, 280-299 |
| 17M | 24 | | PK | | 5-1 | 31-41-13 | D00419 | | 12 | | D05311J | 6 | | | 278 |
| 17N | 24 | | PK | | 7-0 | 31-41-13 | D00419 | | 13 | | TB0100Z | 21 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 17N | 24 | | PK | | 6-10 | 31-41-13 | D00419 | | 13 | | TB0100Z | 21 | BJ | | 278 |
| 17P | 24 | | PK | | 6-0 | 31-41-13 | D00419 | | 14 | | D05311J | 7 | | | 050-099, 150-199, 275-277, 280-299 |
| 17P | 24 | | PK | | 5-1 | 31-41-13 | D00419 | | 14 | | D05311J | 7 | | | 278 |
| 17R | 24 | | PK | | 7-0 | 31-41-13 | D00419 | | 15 | | TB0100Z | 22 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 17R | 24 | | PK | | 6-10 | 31-41-13 | D00419 | | 15 | | TB0100Z | 22 | BJ | | 278 |
| 17S | 24 | | PK | | 6-0 | 31-41-13 | D00419 | | 16 | | D05311J | 8 | | | 050-099, 150-199, 275-277, 280-299 |
| 17S | 24 | | PK | | 5-1 | 31-41-13 | D00419 | | 16 | | D05311J | 8 | | | 278 |
| 17T | 24 | | PK | | 7-0 | 31-41-13 | D00419 | | 17 | | TB0100Z | 22 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 17T | 24 | | PK | | 6-10 | 31-41-13 | D00419 | | 17 | | TB0100Z | 22 | BJ | | 278 |
| 17U | 24 | | PK | | 6-0 | 31-41-13 | D00419 | | 18 | | D05311J | 9 | | | 050-099, 150-199, 275-277, 280-299 |
| 17U | 24 | | PK | | 5-1 | 31-41-13 | D00419 | | 18 | | D05311J | 9 | | | 278 |
| 17Z | 20 | | PA | | 8-0 | 31-41-13 | D00419 | | 23 | | GD04432 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 17Z | 20 | | PA | | 6-9 | 31-41-13 | D00419 | | 23 | | GD04432 | D.. | 2 | | 278 |
| 180 | 24 | | PK | | 5-0 | 21-43-11 | TB0102Y | C033 | BJ | | D05064J | 3 | | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 18
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 180 | 24 | | PK | 5-0 | 21-43-11 | D05064J | | 3 | | | | TB0102Y | C033 | BJ | | 150-199, 275-277, 280-299 |
| 180 | 24 | | PK | 4-1 | 21-43-11 | D05064J | | 3 | | | | TB0102Y | C033 | BJ | | 278 |
| 18A | 24 | | PK | 6-0 | 31-41-13 | D00419 | | 24 | | | | D05311J | 12 | | | 050-099, 150-199, 275-277, 280-299 |
| 18A | 24 | | PK | 5-1 | 31-41-13 | D00419 | | 24 | | | | D05311J | 12 | | | 278 |
| 18B | 20 | | PA | 8-0 | 31-41-13 | D00419 | | 25 | | | | GD04432 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 18B | 20 | | PA | 6-9 | 31-41-13 | D00419 | | 25 | | | | GD04432 | D.. | 2 | | 278 |
| 18C | 24 | | PK | 6-0 | 31-41-13 | D00419 | | 26 | | | | D05311J | 13 | | | 050-099, 150-199, 275-277, 280-299 |
| 18C | 24 | | PK | 5-1 | 31-41-13 | D00419 | | 26 | | | | D05311J | 13 | | | 278 |
| 18D | 20 | | PA | 8-0 | 31-41-13 | D00419 | | 27 | | | | GD04432 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 18D | 20 | | PA | 6-9 | 31-41-13 | D00419 | | 27 | | | | GD04432 | D.. | 2 | | 278 |
| 18E | 24 | | PK | 6-0 | 31-41-13 | D00419 | | 28 | | | | D05311J | 14 | | | 050-099, 150-199, 275-277, 280-299 |
| 18E | 24 | | PK | 5-1 | 31-41-13 | D00419 | | 28 | | | | D05311J | 14 | | | 278 |
| 18F | 24 | | PK | 7-0 | 31-41-13 | D00419 | | 29 | | | | TB0100Z | 22 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 18F | 24 | | PK | 6-10 | 31-41-13 | D00419 | | 29 | | | | TB0100Z | 22 | BJ | | 278 |
| 18G | 24 | | PK | 6-0 | 31-41-13 | D00419 | | 30 | | | | D05311J | 15 | | | 050-099, 150-199, 275-277, 280-299 |
| 18G | 24 | | PK | 5-1 | 31-41-13 | D00419 | | 30 | | | | D05311J | 15 | | | 278 |
| 18J | 24 | | PK | 7-0 | 31-41-13 | D00419 | | 7 | | | | TB0100Z | 22 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 18J | 24 | | PK | 6-10 | 31-41-13 | D00419 | | 7 | | | | TB0100Z | 22 | BJ | | 278 |
| 18K | 24 | | PK | 6-0 | 31-41-13 | D00419 | | 8 | | | | D05311J | 31 | | | 050-099, 150-199, 275-277, 280-299 |
| 18K | 24 | | PK | 5-1 | 31-41-13 | D00419 | | 8 | | | | D05311J | 31 | | | 278 |
| 18L | 20 | | PA | 8-0 | 31-41-13 | D00419 | | 34 | | | | GD04432 | S.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 18L | 20 | | PA | 6-9 | 31-41-13 | D00419 | | 34 | | | | GD04432 | S.. | 2 | | 278 |
| 18M | 24 | | PK | 7-0 | 31-41-13 | D00419 | | 35 | | | | TB0100Z | 22 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 18M | 24 | | PK | 6-10 | 31-41-13 | D00419 | | 35 | | | | TB0100Z | 22 | BJ | | 278 |
| 18N | 24 | | PK | 6-0 | 31-41-13 | D00419 | | 36 | | | | D05311J | 16 | | | 050-099, 150-199, 275-277, 280-299 |
| 18N | 24 | | PK | 5-1 | 31-41-13 | D00419 | | 36 | | | | D05311J | 16 | | | 278 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 19

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 201B | 24 | PL | IA | 3-0 | 21-61-11 | D05726J | | 3 | | D05282J | | 4 | | 050-099, 150-199, 275-277, 280-299 | |
| 201B | 24 | PL | IA | 2-3 | 21-61-11 | D05726J | | 3 | | D05282J | | 4 | | 278 | |
| 201R | 24 | PL | IA | 0-0 | 21-61-11 | D05726J | | 4 | | D05282J | | 5 | | ALL | |
| 202B | 24 | PL | IB | 3-0 | 21-61-11 | D05726J | | 1 | | D05282J | | 2 | | 050-099, 150-199, 275-277, 280-299 | |
| 202B | 24 | PL | IB | 2-3 | 21-61-11 | D05726J | | 1 | | D05282J | | 2 | | 278 | |
| 202R | 24 | PL | IB | 0-0 | 21-61-11 | D05726J | | 2 | | D05282J | | 3 | | ALL | |
| 203B | 24 | PL | IC | 4-0 | 21-61-21 | D05726J | | 7 | | D05180J | | 2 | | 050-099, 150-199, 275-277, 280-299 | |
| 203B | 24 | PL | IC | 3-7 | 21-61-21 | D05726J | | 7 | | D05180J | | 2 | | 278 | |
| 203R | 24 | PL | IC | 0-0 | 21-61-21 | D05726J | | 8 | | D05180J | | 3 | | ALL | |
| 204B | 24 | PL | ID | 4-0 | 21-61-21 | D05726J | | 5 | | D05180J | | 4 | | 050-099, 150-199, 275-277, 280-299 | |
| 204B | 24 | PL | ID | 3-7 | 21-61-21 | D05726J | | 5 | | D05180J | | 4 | | 278 | |
| 204R | 24 | PL | ID | 0-0 | 21-61-21 | D05726J | | 6 | | D05180J | | 5 | | ALL | |
| 206B | 20 | PB | IF | 11-0 | 21-65-11 | D01358 | | 7 | | TB0100X | D002 | BJ | | 050-099 | |
| 206B | 20 | PB | IF | 13-0 | 21-65-11 | D01358 | | 7 | | TB0100X | D002 | BJ | | 150-199, 275-277, 280-299 | |
| 206B | 20 | PB | IF | 12-1 | 21-65-11 | D01358 | | 7 | | TB0100X | D002 | BJ | | 278 | |
| 206R | 20 | PB | IF | 0-0 | 21-65-11 | D01358 | | 8 | | TB0100X | D003 | BJ | | ALL | |
| 207B | 20 | PB | IG | 13-0 | 21-65-11 | D01358 | | 5 | | D05180J | | 13 | | 050-099, 150-199, 275-277, 280-299 | |
| 207B | 20 | PB | IG | 13-2 | 21-65-11 | D01358 | | 5 | | D05180J | | 13 | | 278 | |
| 207R | 20 | PB | IG | 0-0 | 21-65-11 | D01358 | | 6 | | D05180J | | 14 | | ALL | |
| 208B | 20 | PB | IH | 13-0 | 21-65-11 | D01358 | | 9 | | TB0100X | A002 | BJ | | 050-099, 150-199, 275-277, 280-299 | |
| 208B | 20 | PB | IH | 12-1 | 21-65-11 | D01358 | | 9 | | TB0100X | A002 | BJ | | 278 | |
| 208R | 20 | PB | IH | 0-0 | 21-65-11 | D01358 | | 10 | | TB0100X | A003 | BJ | | ALL | |
| 209B | 18 | PB | II | 14-0 | 28-43-11 | D03896 | | 12 | DK | D04714J | | 11 | DK | 050-099, 150-199, 275-277, 280-299 | |
| 209B | 18 | PB | II | 13-4 | 28-43-11 | D03896 | | 12 | DK | D04714J | | 11 | DK | 278 | |
| 209R | 18 | PB | II | 0-0 | 28-43-11 | D03896 | | 13 | DK | D04714J | | 12 | DK | ALL | |
| 210B | 24 | PW | IJ | 13-0 | 36-21-11 | D03892 | | 6 | | TB0102X | B003 | BJ | | 050-099, 150-199, 275-277, 280-299 | |
| 210B | 24 | PW | IJ | 13-1 | 36-21-11 | D03892 | | 6 | | TB0102X | B003 | BJ | | 278 | |
| 210R | 24 | PW | IJ | 0-0 | 36-21-11 | D03892 | | 5 | | TB0102X | B002 | BJ | | ALL | |
| 210Z | | | IJ | 0-0 | 36-21-11 | D03892 | | DED | | TB0102X | DED | | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 20
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 211B | 24 | PL | IK | 14-0 | 36-21-11 | D03892 | | 4 | | | D05726J | 41 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 211B | 24 | PL | IK | 13-5 | 36-21-11 | D03892 | | 4 | | | D05726J | 41 | | | 278 |
| 211R | 24 | PL | IK | 0-0 | 36-21-11 | D03892 | | 3 | | | D05726J | 40 | | | ALL |
| 213B | 24 | PW | IM | 5-0 | 23-41-11 | D01431 | | 5 | | | D04955J | 17 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 213B | 24 | PW | IM | 3-9 | 23-41-11 | D01431 | | 5 | | | D04955J | 17 | | | 278 |
| 213R | 24 | PW | IM | 0-0 | 23-41-11 | D01431 | | 6 | | | D04955J | 16 | | | ALL |
| 213Z | | | IM | 0-0 | 23-41-11 | D01431 | | DED | | | D04955J | | | FB | ALL |
| 214B | 24 | PW | IN | 5-0 | 23-41-11 | D01431 | | 8 | | | D04955J | 15 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 214B | 24 | PW | IN | 3-9 | 23-41-11 | D01431 | | 8 | | | D04955J | 15 | | | 278 |
| 214R | 24 | PW | IN | 0-0 | 23-41-11 | D01431 | | 7 | | | D04955J | 14 | | | ALL |
| 214Z | | | IN | 0-0 | 23-41-11 | D01431 | | DED | | | D04955J | | | FB | ALL |
| 223B | 24 | PL | IP | 5-0 | 21-61-71 | D05180J | | 27 | | | D04644J | 49 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 223B | 24 | PL | IP | 3-8 | 21-61-71 | D05180J | | 27 | | | D04644J | 49 | | | 278 |
| 223R | 24 | PL | IP | 0-0 | 21-61-71 | D05180J | | 28 | | | D04644J | 50 | | | ALL |
| 224B | 24 | PL | IR | 5-0 | 21-61-71 | D05180J | | 30 | | | D04644J | 52 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 224B | 24 | PL | IR | 3-8 | 21-61-71 | D05180J | | 30 | | | D04644J | 52 | | | 278 |
| 224R | 24 | PL | IR | 0-0 | 21-61-71 | D05180J | | 29 | | | D04644J | 51 | | | ALL |
| 226B | 24 | PL | JA | 5-0 | 23-51-41 | D00551 | | 13 | | | D00557 | 19 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 226B | 24 | PL | JA | 4-0 | 23-51-41 | D00551 | | 13 | | | D00557 | 19 | | | 278 |
| 226R | 24 | PL | JA | 0-0 | 23-51-41 | D00551 | | 14 | | | D00557 | 18 | | | ALL |
| 227B | 24 | PW | JB | 5-0 | 23-51-41 | D00551 | | 12 | | | D00557 | 3 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 227B | 24 | PW | JB | 4-0 | 23-51-41 | D00551 | | 12 | | | D00557 | 3 | | | 278 |
| 227R | 24 | PW | JB | 0-0 | 23-51-41 | D00551 | | 10 | | | D00557 | 4 | | | ALL |
| 227Z | | | JB | 0-0 | 23-51-41 | D00551 | | 11 | | | D00557 | 5 | | | 050-099 |
| 227Z | | | JB | 0-0 | 23-51-41 | D00551 | | | | FZ | D00557 | | | FY | 150-199, 275-299 |
| 228B | 20 | PB | AL | 4-0 | 21-65-11 | D05400J | | 8 | | | D05180J | 31 | | | 050-099 |
| 228B | 20 | PB | IT | 4-0 | 21-65-11 | D05180J | | 31 | | | D05400J | 8 | | | 150-199, 275-277, 280-299 278 |
| 228B | 20 | PB | IT | 3-3 | 21-65-11 | D05180J | | 31 | | | D05400J | 8 | | | 278 |
| 228R | 20 | PB | AL | 0-0 | 21-65-11 | D05400J | | 2 | | | D05180J | 32 | | | 050-099 |
| 228R | 20 | PB | IT | 0-0 | 21-65-11 | D05180J | | 32 | | | D05400J | 2 | | | 150-199, 275-299 |
| 229B | 20 | PB | AM | 4-0 | 21-65-11 | D05400J | | 10 | | | D05180J | 33 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 21

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----|--|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 229B | 20 | PB | IU | 4-0 | 21-65-11 | D05180J | | 33 | | | | D05400J | 10 | | | 150-199, 275-277, 280-299 |
| 229B | 20 | PB | IU | 3-3 | 21-65-11 | D05180J | | 33 | | | | D05400J | 10 | | | 278 |
| 229R | 20 | PB | AM | 0-0 | 21-65-11 | D05400J | | 9 | | | | D05180J | 34 | | | 050-099 |
| 229R | 20 | PB | IU | 0-0 | 21-65-11 | D05180J | | 34 | | | | D05400J | 9 | | | 150-199, 275-299 |
| 230B | 24 | PL | JE | 5-0 | 28-41-13 | D04718J | | 6 | | | | TB0100X | C005 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 230B | 24 | PL | JE | 4-7 | 28-41-13 | D04718J | | 6 | | | | TB0100X | C005 | BJ | | 278 |
| 230R | 24 | PL | JE | 0-0 | 28-41-13 | D04718J | | 7 | | | | TB0100X | D005 | BJ | | ALL |
| 233B | 22 | PB | JH | 5-0 | 21-51-12 | D05180J | | 15 | | | | D04708J | 33 | | | 050-099, 150-199, 275-277, 280-299 |
| 233B | 22 | PB | JH | 3-9 | 21-51-12 | D05180J | | 15 | | | | D04708J | 33 | | | 278 |
| 233R | 22 | PB | JH | 0-0 | 21-51-12 | D05180J | | 16 | | | | D04708J | 34 | | | ALL |
| 234B | 24 | PL | JI | 2-0 | 33-13-16 | TB0278R | | C001 | 2 | | | D10404 | B3 | | | 050-099, 150-199, 275-277, 280-299 |
| 234B | 24 | PL | JI | 1-9 | 33-13-16 | TB0278R | | C001 | 2 | | | D10404 | B3 | | | 278 |
| 234R | 24 | PL | JI | 0-0 | 33-13-16 | TB0278R | | A001 | 2 | | | D10404 | A3 | | | ALL |
| 239 | 20 | UA | | 5-0 | 23-22-15 | TB0098X | | | | | GD | GD04432 | S.. | 2 | | 050-099 |
| 239 | 20 | UA | | 5-0 | 23-22-15 | TB0098X | | REF | | | GD | GD04432 | S.. | 2 | | 150-154 |
| 239 | 20 | UA | | 4-0 | 23-22-15 | TB0098X | | REF | | | GD | GD04432 | S.. | 2 | | 155-199, 275-277, 280-299 |
| 239 | 20 | UA | | 3-6 | 23-22-15 | TB0098X | | REF | | | GD | GD04432 | S.. | 2 | | 278 |
| 239B | 24 | PW | DJ | 5-0 | 23-22-15 | TB0098X | | B022 | BJ | | | D04955J | 7 | | | 050-099 |
| 239B | 24 | PW | DJ | 7-0 | 23-22-15 | TB0098X | | B022 | BJ | | | D04955J | 7 | | | 150-154 |
| 239B | 24 | PW | DJ | 6-0 | 23-22-15 | TB0098X | | B022 | BJ | | | D04955J | 7 | | | 155-199, 275-277, 280-299 |
| 239B | 24 | PW | DJ | 4-3 | 23-22-15 | TB0098X | | B022 | BJ | | | D04955J | 7 | | | 278 |
| 239R | 24 | PW | DJ | 0-0 | 23-22-15 | TB0098X | | A022 | BJ | | | D04955J | 6 | | | 050-099, 155-199, 275-299 |
| 239R | 24 | PW | DJ | 0-0 | 23-22-15 | TB0098X | | A022 | BJ | | | D04955J | 10 | | | 150-154 |
| 239Z | | | DJ | 0-0 | 23-22-15 | TB0098X | | | | | GD | D04955J | 9 | | | 050-099 |
| 239Z | | | DJ | 0-0 | 23-22-15 | TB0098X | | REF | | | GD | D04955J | 9 | | | 150-199, 275-299 |
| 288 | 20 | PA | | 8-0 | 73-21-11 | GD04426 | | D.. | 2 | | | D11800 | 3 | | | 050-099, 155-199, 275-277 |
| 288 | 20 | PA | | 6-0 | 73-21-11 | GD04426 | | D.. | 2 | | | D11800 | 3 | | | 150-154 |
| 288 | 20 | PA | | 7-7 | 73-21-11 | GD04426 | | D.. | 2 | | | D11800 | 3 | | | 278 |
| 288 | 20 | PA | J | 8-0 | 73-21-11 | GD04426 | | D.. | 2 | | | D11800 | 3 | | | 280-299 |
| 291 | 20 | PA | | 5-0 | 73-21-11 | D04720J | | 15 | | | | D11800 | 4 | | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 22
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 291 | 20 | | PA | 6-0 | 73-21-11 | D04720J | | 15 | | | D11800 | | 4 | | 150-199, 275-277, 280-299 | |
| 291 | 20 | | PA | 4-11 | 73-21-11 | D04720J | | 15 | | | D11800 | | 4 | | 278 | |
| 295B | 24 | | PL AF | 5-0 | 21-61-61 | D05180J | | 11 | | | D04644J | | 47 | | 050-099 | |
| 295B | 24 | | PL IV | 5-0 | 21-61-61 | D05180J | | 11 | | | D04644J | | 47 | | 150-199, 275-277, 280-299 | |
| 295B | 24 | | PL IV | 3-8 | 21-61-61 | D05180J | | 11 | | | D04644J | | 47 | | 278 | |
| 295R | 24 | | PL AF | 0-0 | 21-61-61 | D05180J | | 10 | | | D04644J | | 48 | | 050-099 | |
| 295R | 24 | | PL IV | 0-0 | 21-61-61 | D05180J | | 10 | | | D04644J | | 48 | | 150-199, 275-299 | |
| 296B | 24 | | PL AG | 5-0 | 21-61-61 | D05180J | | 26 | | | D04644J | | 45 | | 050-099 | |
| 296B | 24 | | PL IW | 5-0 | 21-61-61 | D05180J | | 26 | | | D04644J | | 45 | | 150-199, 275-277, 280-299 | |
| 296B | 24 | | PL IW | 3-8 | 21-61-61 | D05180J | | 26 | | | D04644J | | 45 | | 278 | |
| 296R | 24 | | PL AG | 0-0 | 21-61-61 | D05180J | | 25 | | | D04644J | | 46 | | 050-099 | |
| 296R | 24 | | PL IW | 0-0 | 21-61-61 | D05180J | | 25 | | | D04644J | | 46 | | 150-199, 275-299 | |
| 301B | 24 | | PM MA | 14-0 | 21-64-11 | D01302 | | 9 | | | D05400J | | 12 | | 050-099, 150-199, 275-277, 280-299 | |
| 301B | 24 | | PM MA | 12-8 | 21-64-11 | D01302 | | 9 | | | D05400J | | 12 | | 278 | |
| 301R | 24 | | PM MA | 0-0 | 21-64-11 | D01302 | | 8 | | | D05400J | | 13 | | ALL | |
| 301Y | 24 | | PM MA | 0-0 | 21-64-11 | D01302 | | 10 | | | D05400J | | 14 | | ALL | |
| 303B | 24 | | PM MC | 8-0 | 33-13-16 | D00874 | | 16 | | | TB0064Z | | 14 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 303B | 24 | | PM MC | 8-2 | 33-13-16 | D00874 | | 16 | | | TB0064Z | | 14 | BJ | 278 | |
| 303R | 24 | | PM MC | 0-0 | 33-13-16 | D00874 | | 1 | | | TB0064Z | | 13 | BJ | ALL | |
| 303Y | 24 | | PM MC | 0-0 | 33-13-16 | D00874 | | 2 | | | TB0064Z | | 15 | BJ | ALL | |
| 307B | 24 | | PM MG | 8-0 | 33-13-16 | D00898 | | 5 | | | TB0064Z | | 14 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 307B | 24 | | PM MG | 8-5 | 33-13-16 | D00898 | | 5 | | | TB0064Z | | 14 | BJ | 278 | |
| 307R | 24 | | PM MG | 0-0 | 33-13-16 | D00898 | | 6 | | | TB0064Z | | 13 | BJ | ALL | |
| 307Y | 24 | | PM MG | 0-0 | 33-13-16 | D00898 | | 1 | | | TB0064Z | | 15 | BJ | ALL | |
| 308B | 24 | | PM MH | 7-0 | 33-13-16 | D00896 | | 5 | | | TB0064Z | | 14 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 308B | 24 | | PM MH | 6-10 | 33-13-16 | D00896 | | 5 | | | TB0064Z | | 14 | BJ | 278 | |
| 308R | 24 | | PM MH | 0-0 | 33-13-16 | D00896 | | 6 | | | TB0064Z | | 13 | BJ | ALL | |
| 308Y | 24 | | PM MH | 0-0 | 33-13-16 | D00896 | | 1 | | | TB0064Z | | 15 | BJ | ALL | |
| 309B | 24 | | PM MI | 7-0 | 33-13-16 | D00548 | | 5 | | | TB0064Z | | 14 | BJ | ALL | |
| 309R | 24 | | PM MI | 0-0 | 33-13-16 | D00548 | | 6 | | | TB0064Z | | 13 | BJ | ALL | |
| 309Y | 24 | | PM MI | 0-0 | 33-13-16 | D00548 | | 1 | | | TB0064Z | | 15 | BJ | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 23

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 310B | 24 | | PM | MJ | 4-0 | 33-13-16 | D00550 | | 5 | | | | D10404 | C2 | | 050-099, 150-199, 275-277, 280-299 |
| 310B | 24 | | PM | MJ | 3-0 | 33-13-16 | D00550 | | 5 | | | | D10404 | C2 | | 278 |
| 310R | 24 | | PM | MJ | 0-0 | 33-13-16 | D00550 | | 6 | | | | D10404 | A2 | | ALL |
| 310Y | 24 | | PM | MJ | 0-0 | 33-13-16 | D00550 | | 1 | | | | D10404 | B2 | | ALL |
| 311B | 24 | | PM | MK | 5-0 | 33-13-16 | D00558 | | 5 | | | | TB0064Z | 14 | BJ | 050-099, 150-199, 275-277, 280-299 |
| 311B | 24 | | PM | MK | 3-11 | 33-13-16 | D00558 | | 5 | | | | TB0064Z | 14 | BJ | 278 |
| 311R | 24 | | PM | MK | 0-0 | 33-13-16 | D00558 | | 6 | | | | TB0064Z | 13 | BJ | ALL |
| 311Y | 24 | | PM | MK | 0-0 | 33-13-16 | D00558 | | 1 | | | | TB0064Z | 15 | BJ | ALL |
| 312B | 24 | | PM | ML | 8-0 | 33-13-19 | D05000P | | 10 | | | | D00874 | 6 | | 050-099, 150-199, 275-277, 280-299 |
| 312B | 24 | | PM | ML | 7-9 | 33-13-19 | D05000P | | 10 | | | | D00874 | 6 | | 278 |
| 312R | 24 | | PM | ML | 0-0 | 33-13-19 | D05000P | | 22 | | | | D00874 | 10 | | ALL |
| 312Y | 24 | | PM | ML | 0-0 | 33-13-19 | D05000P | | 24 | | | | D00874 | 11 | | ALL |
| 313B | 24 | | PM | MM | 6-0 | 33-13-18 | D05282J | | 19 | | | | TB0100X | D007 | BJ | 050-099, 150-199, 275-277, 280-299 |
| 313B | 24 | | PM | MM | 4-5 | 33-13-18 | D05282J | | 19 | | | | TB0100X | D007 | BJ | 278 |
| 313R | 24 | | PM | MM | 0-0 | 33-13-18 | D05282J | | 18 | | | | TB0100X | D006 | BJ | ALL |
| 313Y | 24 | | PM | MM | 0-0 | 33-13-18 | D05282J | | 20 | | | | TB0100X | D008 | BJ | ALL |
| 315B | 24 | | PM | MO | 9-0 | 33-13-16 | TB0064Z | | 14 | BJ | | | D10404 | C1 | | 050-099, 150-199, 275-277, 280-299 |
| 315B | 24 | | PM | MO | 8-1 | 33-13-16 | TB0064Z | | 14 | BJ | | | D10404 | C1 | | 278 |
| 315R | 24 | | PM | MO | 0-0 | 33-13-16 | TB0064Z | | 13 | BJ | | | D10404 | A1 | | ALL |
| 315Y | 24 | | PM | MO | 0-0 | 33-13-16 | TB0064Z | | 15 | BJ | | | D10404 | B1 | | ALL |
| 316B | 24 | | PM | AE | 13-0 | 21-61-81 | D13572 | | 1 | | | | D04726J | 31 | | 050-099 |
| 316B | 24 | | PM | AE | 14-0 | 21-61-81 | D13572 | | 1 | | | | D04726J | 31 | | 150-199, 275-277, 280-299 |
| 316B | 24 | | PM | AE | 13-4 | 21-61-81 | D13572 | | 1 | | | | D04726J | 31 | | 278 |
| 316R | 24 | | PM | AE | 0-0 | 21-61-81 | D13572 | | 2 | | | | D04726J | 32 | | ALL |
| 316Y | 24 | | PM | AE | 0-0 | 21-61-81 | D13572 | | 3 | | | | D04726J | 33 | | ALL |
| 338B | 24 | | PM | AT | 5-0 | 21-61-61 | TB0096X | | A003 | BJ | | | D04644J | 42 | | 050-099 |
| 338B | 24 | | PM | IE | 5-0 | 21-61-61 | D04644J | | 42 | | | | TB0096X | A003 | BJ | 150-199, 275-277, 280-299 |
| 338B | 24 | | PM | IE | 4-8 | 21-61-61 | D04644J | | 42 | | | | TB0096X | A003 | BJ | 278 |
| 338R | 24 | | PM | AT | 0-0 | 21-61-61 | TB0096X | | B003 | BJ | | | D04644J | 43 | | 050-099 |
| 338R | 24 | | PM | IE | 0-0 | 21-61-61 | D04644J | | 43 | | | | TB0096X | B003 | BJ | 150-199, 275-299 |
| 338Y | 24 | | PM | AT | 0-0 | 21-61-61 | TB0096X | | C003 | BJ | | | D04644J | 44 | | 050-099 |
| 338Y | 24 | | PM | IE | 0-0 | 21-61-61 | D04644J | | 44 | | | | TB0096X | C003 | BJ | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 24

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 339B | 24 | PM | AI | 11-0 | 21-61-71 | TB0066X | B014 | BJ | | D04644J | 53 | | | 050-099 | | |
| 339B | 24 | PM | IS | 11-0 | 21-61-71 | D04644J | 53 | | | TB0066X | B014 | BJ | | 150-199 | | |
| 339B | 24 | PM | IS | 10-0 | 21-61-71 | D04644J | 53 | | | TB0066X | B014 | BJ | | 275-277, 280-299 | | |
| 339B | 24 | PM | IS | 10-4 | 21-61-71 | D04644J | 53 | | | TB0066X | B014 | BJ | | 278 | | |
| 339R | 24 | PM | AI | 0-0 | 21-61-71 | TB0066X | C014 | BJ | | D04644J | 54 | | | 050-099 | | |
| 339R | 24 | PM | IS | 0-0 | 21-61-71 | D04644J | 54 | | | TB0066X | C014 | BJ | | 150-199, 275-299 | | |
| 339Y | 24 | PM | AI | 0-0 | 21-61-71 | TB0066X | D014 | BJ | | D04644J | 55 | | | 050-099 | | |
| 339Y | 24 | PM | IS | 0-0 | 21-61-71 | D04644J | 55 | | | TB0066X | D014 | BJ | | 150-199, 275-299 | | |
| 401B | 22 | PT | QA | 13-0 | 21-31-11 | D01324 | 8 | | | D05186J | 24 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 401B | 22 | PT | QA | 13-2 | 21-31-11 | D01324 | 8 | | | D05186J | 24 | | | 278 | | |
| 401G | 22 | PT | QA | 0-0 | 21-31-11 | D01324 | 20 | | | D05186J | 25 | | | ALL | | |
| 401R | 22 | PT | QA | 0-0 | 21-31-11 | D01324 | 9 | | | D05186J | 26 | | | ALL | | |
| 401Y | 22 | PT | QA | 0-0 | 21-31-11 | D01324 | 21 | | | D05186J | 27 | | | ALL | | |
| 401Z | 22 | PT | QA | 0-0 | 21-31-11 | D01324 | | | FQ | D05186J | 28 | | | ALL | | |
| 402B | 22 | PT | QB | 14-0 | 21-31-21 | D01324 | 10 | | | D04710J | 32 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 402B | 22 | PT | QB | 13-7 | 21-31-21 | D01324 | 10 | | | D04710J | 32 | | | 278 | | |
| 402G | 22 | PT | QB | 0-0 | 21-31-21 | D01324 | 22 | | | D04710J | 33 | | | ALL | | |
| 402R | 22 | PT | QB | 0-0 | 21-31-21 | D01324 | 11 | | | D04710J | 34 | | | ALL | | |
| 402Y | 22 | PT | QB | 0-0 | 21-31-21 | D01324 | 23 | | | D04710J | 35 | | | ALL | | |
| 402Z | 22 | PT | QB | 0-0 | 21-31-21 | D01324 | | | FR | D04710J | 36 | | | ALL | | |
| 403B | 24 | PN | QC | 9-0 | 24-23-11 | D05848P | 8 | | | D04778J | 3 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 403B | 24 | PN | QC | 8-4 | 24-23-11 | D05848P | 8 | | | D04778J | 3 | | | 278 | | |
| 403G | 24 | PN | QC | 0-0 | 24-23-11 | D05848P | 7 | | | D04778J | 4 | | | ALL | | |
| 403R | 24 | PN | QC | 0-0 | 24-23-11 | D05848P | 6 | | | D04778J | 5 | | | ALL | | |
| 403Y | 24 | PN | QC | 0-0 | 24-23-11 | D05848P | 5 | | | D04778J | 6 | | | ALL | | |
| 405R | 22 | PH | | 12-0 | 26-18-11 | TB0100D | A009 | 2 | | SM00004 | | 9 | | 150-157, 275-277, 280-299 | | |
| 405R | 22 | PH | | 3-10 | 26-18-11 | TB0100D | A009 | 2 | | SM00004 | | 9 | | 278 | | |
| 406R | 22 | PH | | 7-0 | 26-18-12 | D04644J | 36 | | | TB0100D | A009 | 2 | | 050-099 | | |
| 406R | 22 | PH | | 0-24 | 26-18-12 | D04644J | 36 | | | SM00004 | | 9 | | 150-157, 275-299 | | |
| 406R | 22 | PH | | 5-0 | 26-18-12 | D04644J | 36 | | | TB0100D | A009 | 2 | | 162-199 | | |
| 407R | 22 | PH | | 4-0 | 26-18-12 | D04644J | 37 | | | TB0102X | A009 | BJ | | 050-099, 150-199, 275-277, 280-299 | | |
| 407R | 22 | PH | | 4-3 | 26-18-12 | D04644J | 37 | | | TB0102X | A009 | BJ | | 278 | | |
| 412R | 22 | PH | | 5-0 | 26-18-12 | D04726J | 9 | | | TB0102X | C008 | BJ | | 050-099 | | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 25

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 412R | 22 | | PH | | 4-0 | 26-18-12 | D04726J | | 9 | | TB0102X | C008 | BJ | | 150-199, 275-277, 280-299 |
| 412R | 22 | | PH | | 4-6 | 26-18-12 | D04726J | | 9 | | TB0102X | C008 | BJ | | 278 |
| 413R | 22 | | PH | | 5-0 | 26-18-12 | D04726J | | 10 | | TB0102X | D008 | BJ | | 050-099 |
| 413R | 22 | | PH | | 4-0 | 26-18-12 | D04726J | | 10 | | TB0102X | D008 | BJ | | 150-199, 275-277, 280-299 |
| 413R | 22 | | PH | | 4-6 | 26-18-12 | D04726J | | 10 | | TB0102X | D008 | BJ | | 278 |
| 414R | 22 | | PH | | 6-0 | 26-18-22 | D10222 | | 1 | | TB0102X | B009 | BJ | | 050-099, 275-277, 280-299 |
| 414R | 22 | | PH | | 13-0 | 26-18-22 | D10222 | | 1 | | TB0102X | B009 | BJ | | 150-199 |
| 414R | 22 | | PH | | 6-5 | 26-18-22 | D10222 | | 1 | | TB0102X | B009 | BJ | | 278 |
| 500 | 22 | | PQ | AV | 13-0 | 28-22-31 | D01330 | | 19 | | TB0104X | A038 | BJ | | 050-099 |
| 500 | 22 | | PQ | AY | 13-0 | 28-22-31 | D01330 | | 19 | | TB0104X | A038 | BJ | | 150-199, 275-299 |
| 500Z | | | | AV | 0-0 | 28-22-31 | D01330 | | DED | | TB0104X | DED | | | 050-099 |
| 500Z | | | | AY | 0-0 | 28-22-31 | D01330 | | DED | | TB0104X | DED | | | 150-199, 275-299 |
| 501 | 18 | | PA | | 7-0 | 33-13-16 | D01302 | | 1 | DK | TB0068H | | 6 | 2 | 050-099, 150-199, 275-277, 280-299 |
| 501 | 18 | | PA | | 7-7 | 33-13-16 | D01302 | | 1 | DK | TB0068H | | 6 | 2 | 278 |
| 502 | 18 | | PA | | 9-0 | 33-13-16 | D01302 | | 2 | DK | GD00086 | | A.. | 2 | 050-099, 150-199, 275-277, 280-299 |
| 502 | 18 | | PA | | 7-4 | 33-13-16 | D01302 | | 2 | DK | GD00086 | | A.. | 2 | 278 |
| 503 | 22 | | PA | | 9-0 | 33-16-17 | TB0070Z | | 29 | BJ | D01302 | | 3 | | 050-099, 150-199, 275-277, 280-299 |
| 503 | 22 | | PA | | 7-7 | 33-16-17 | TB0070Z | | 29 | BJ | D01302 | | 3 | | 278 |
| 504 | 22 | | PA | | 9-0 | 33-16-17 | TB0070Y | | C035 | BJ | D01302 | | 4 | | 050-099, 150-199, 275-277, 280-299 |
| 504 | 22 | | PA | | 7-7 | 33-16-17 | TB0070Y | | C035 | BJ | D01302 | | 4 | | 278 |
| 505 | 24 | | PK | | 13-0 | 21-24-11 | D04708J | | 28 | | D01302 | | 5 | | 050-099 |
| 505 | 24 | | PK | | 13-0 | 21-24-11 | D01302 | | 5 | | D04708J | | 28 | | 150-199 |
| 506 | 22 | | PA | | 13-0 | 21-24-11 | D01302 | | 6 | | TB0100Y | A037 | BJ | | 050-099 |
| 506 | 22 | | PA | | 12-0 | 21-24-11 | D01302 | | 6 | | TB0100Y | A037 | BJ | | 150-199 |
| 507 | 22 | | PA | | 7-0 | 33-16-17 | D01302 | | 25 | | TB0070Y | A032 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 507 | 22 | | PA | | 7-7 | 33-16-17 | D01302 | | 25 | | TB0070Y | A032 | BJ | | 278 |
| 508 | 22 | | PA | | 7-0 | 33-16-17 | D01302 | | 26 | | TB0070Y | C032 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 508 | 22 | | PA | | 7-7 | 33-16-17 | D01302 | | 26 | | TB0070Y | C032 | BJ | | 278 |
| 509 | 20 | | PA | | 6-0 | 24-51-72 | D05726J | | 47 | | TB0100Y | C011 | BJ | | 050-099 |
| 509 | 20 | | PA | | 5-0 | 24-51-72 | D05726J | | 47 | | TB0100Y | C011 | BJ | | 162-164, 276 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 26
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 50A | 24 | | PK | 4-0 | 21-25-11 | D07960J | | 1 | | | | | D04644J | 3 | | | 050-099, 150-199, 275-277, 280-299 |
| 50A | 24 | | PK | 3-5 | 21-25-11 | D07960J | | 1 | | | | | D04644J | 3 | | | 278 |
| 50B | 22 | | PA | 5-0 | 21-25-11 | TB0100Y | A040 | BJ | | | | | D04644J | 4 | | | 050-099, 150-199, 275-277, 280-299 |
| 50B | 22 | | PA | 4-3 | 21-25-11 | TB0100Y | A040 | BJ | | | | | D04644J | 4 | | | 278 |
| 50C | 22 | | PA | 5-0 | 21-25-11 | TB0100Y | A040 | BJ | | | | | D04644J | 2 | | | 050-099, 150-199, 275-277, 280-299 |
| 50C | 22 | | PA | 4-3 | 21-25-11 | TB0100Y | A040 | BJ | | | | | D04644J | 2 | | | 278 |
| 50D | 24 | | PK | 5-0 | 21-25-11 | D04644J | | 19 | | | | | TB0098Y | A014 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 50D | 24 | | PK | 4-3 | 21-25-11 | D04644J | | 19 | | | | | TB0098Y | A014 | BJ | | 278 |
| 50E | 24 | | PK | 4-0 | 21-26-11 | TB0100Y | C040 | BJ | | | | | D07960J | 2 | | | 050-099, 150-199, 275-277, 280-299 |
| 50E | 24 | | PK | 3-4 | 21-26-11 | TB0100Y | C040 | BJ | | | | | D07960J | 2 | | | 278 |
| 50G | 24 | | PK | 6-0 | 21-26-11 | TB0100Y | C040 | BJ | | | | | D04708J | 45 | | | 050-099, 150-199, 275-277, 280-299 |
| 50G | 24 | | PK | 4-3 | 21-26-11 | TB0100Y | C040 | BJ | | | | | D04708J | 45 | | | 278 |
| 50H | 20 | | PA | 5-0 | 21-31-11 | TB0100Y | A039 | BJ | | | | | D05064J | 33 | | | 050-099, 150-199, 275-277, 280-299 |
| 50H | 20 | | PA | 4-0 | 21-31-11 | TB0100Y | A039 | BJ | | | | | D05064J | 33 | | | 278 |
| 50J | 20 | | PA | 6-0 | 21-31-11 | TB0100Y | A039 | BJ | | | | | D05186J | 19 | | | 050-099, 150-199, 275-277, 280-299 |
| 50J | 20 | | PA | 4-4 | 21-31-11 | TB0100Y | A039 | BJ | | | | | D05186J | 19 | | | 278 |
| 50K | 20 | | PA | 6-0 | 21-31-21 | TB0100Y | A016 | BJ | | | | | D04710J | 40 | | | 050-099, 150-199, 275-277, 280-299 |
| 50K | 20 | | PA | 4-9 | 21-31-21 | TB0100Y | A016 | BJ | | | | | D04710J | 40 | | | 278 |
| 50L | 24 | | PK | 5-0 | 21-33-11 | TB0100Z | | 20 | BJ | | | | D05400J | 15 | | | 050-099, 150-199, 275-277, 280-299 |
| 50L | 24 | | PK | 3-9 | 21-33-11 | TB0100Z | | 20 | BJ | | | | D05400J | 15 | | | 278 |
| 50M | 22 | | PA | 6-0 | 21-33-11 | TB0100Z | | 20 | BJ | | | | D05282J | 12 | | | 050-099, 150-199, 275-277, 280-299 |
| 50M | 22 | | PA | 4-5 | 21-33-11 | TB0100Z | | 20 | BJ | | | | D05282J | 12 | | | 278 |
| 50N | 24 | | PK | 5-0 | 21-43-11 | TB0104Y | A014 | BJ | | | | | D05064J | 28 | | | 050-099, 150-199 |
| 50N | 24 | | PK | 4-0 | 21-43-11 | TB0104Y | A014 | BJ | | | | | D05064J | 28 | | | 275-277, 280-299 |
| 50N | 24 | | PK | 4-4 | 21-43-11 | TB0104Y | A014 | BJ | | | | | D05064J | 28 | | | 278 |
| 50P | 24 | | PK | 4-0 | 21-44-11 | TB0102X | A002 | BJ | | | | | D05064J | 31 | | | 050-099, 150-199, 275-277, 280-299 |
| 50P | 24 | | PK | 4-1 | 21-44-11 | TB0102X | A002 | BJ | | | | | D05064J | 31 | | | 278 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 27

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 50R | 24 | | PK | | 5-0 | SPARE | D04644J | CAP | Y | | TB0098X | CAP | Y | | 051-099, 150-154 |
| 50R | 24 | | PK | | 5-0 | 21-44-21 | D04644J | | 59 | | TB0098X | D008 | BJ | | 275-276 |
| 50S | 24 | | PK | | 7-0 | SPARE | D04644J | CAP | Y | | TB0106Y | CAP | Y | | 051-099, 150-154 |
| 50S | 24 | | PK | | 7-0 | 21-44-21 | D04644J | | 8 | | TB0106Y | C014 | BJ | | 275-276 |
| 50T | 20 | | PA | | 4-0 | 21-45-11 | D04968P | | 13 | | D04966P | | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 50T | 20 | | PA | | 1-10 | 21-45-11 | D04968P | | 13 | | D04966P | | 2 | | 278 |
| 50U | 20 | | PA | | 4-0 | 21-45-11 | D04968P | | 14 | | D04966P | | 3 | | 050-099, 150-199, 275-277, 280-299 |
| 50U | 20 | | PA | | 1-10 | 21-45-11 | D04968P | | 14 | | D04966P | | 3 | | 278 |
| 50V | 22 | | PA | | 5-0 | 21-51-11 | D07960J | | 3 | | D04644J | | 18 | | 050-099, 150-199, 275-277, 280-299 |
| 50V | 22 | | PA | | 3-5 | 21-51-11 | D07960J | | 3 | | D04644J | | 18 | | 278 |
| 50W | 24 | | PK | | 5-0 | 21-51-23 | D07960J | | 4 | | D04708J | | 29 | | 050-099, 150-199, 275-277, 280-299 |
| 50W | 24 | | PK | | 3-6 | 21-51-23 | D07960J | | 4 | | D04708J | | 29 | | 278 |
| 50X | 24 | | PK | | 5-0 | 21-51-23 | D07960J | | 5 | | D04708J | | 30 | | 050-099, 150-199, 275-277, 280-299 |
| 50X | 24 | | PK | | 3-6 | 21-51-23 | D07960J | | 5 | | D04708J | | 30 | | 278 |
| 50Y | 24 | | PK | | 4-0 | 21-52-41 | D07960J | | 6 | | D05064J | | 18 | | 050-099, 150-199, 275-277, 280-299 |
| 50Y | 24 | | PK | | 3-3 | 21-52-41 | D07960J | | 6 | | D05064J | | 18 | | 278 |
| 50Z | 24 | | PK | | 4-0 | 21-53-11 | D07960J | | 8 | | D05064J | | 25 | | 050-099, 150-199, 275-277, 280-299 |
| 50Z | 24 | | PK | | 3-3 | 21-53-11 | D07960J | | 8 | | D05064J | | 25 | | 278 |
| 511 | 20 | | PA | | 9-0 | 21-64-11 | D01302 | | 11 | | GD00084 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 511 | 20 | | PA | | 7-2 | 21-64-11 | D01302 | | 11 | | GD00084 | D.. | 2 | | 278 |
| 512 | 22 | | PA | | 14-0 | 21-64-11 | D01302 | | 12 | | TB0102Y | A016 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 512 | 22 | | PA | | 12-9 | 21-64-11 | D01302 | | 12 | | TB0102Y | A016 | BJ | | 278 |
| 513 | 22 | | PA | | 13-0 | 21-51-11 | D01302 | | 13 | | D04644J | | 27 | | 050-099, 150-199, 275-277, 280-299 |
| 513 | 22 | | PA | | 13-1 | 21-51-11 | D01302 | | 13 | | D04644J | | 27 | | 278 |
| 514 | 22 | | PA | | 13-0 | 21-51-11 | D01302 | | 14 | | D04644J | | 26 | | 050-099, 150-199, 275-277, 280-299 |
| 514 | 22 | | PA | | 13-1 | 21-51-11 | D01302 | | 14 | | D04644J | | 26 | | 278 |
| 515 | 24 | | PK | | 13-0 | 21-51-11 | D01302 | | 15 | | D04644J | | 25 | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 28

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 515 | 24 | | PK | 13-1 | 21-51-11 | D01302 | | 15 | | | | | D04644J | 25 | | | 278 |
| 516 | 24 | | PK | 13-0 | 21-25-11 | D01302 | | 16 | | | | | D04644J | 5 | | | 050-099, 150-199, 275-277, 280-299 |
| 516 | 24 | | PK | 13-1 | 21-25-11 | D01302 | | 16 | | | | | D04644J | 5 | | | 278 |
| 517 | 22 | | PA | 15-0 | 21-25-11 | D01302 | | 17 | | | | | TB0100Y | A040 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 517 | 22 | | PA | 12-8 | 21-25-11 | D01302 | | 17 | | | | | TB0100Y | A040 | BJ | | 278 |
| 518 | 24 | | PK | 15-0 | 21-53-11 | D07960J | | 7 | | | | | D01302 | 18 | | | 050-099, 150-199, 275-277, 280-299 |
| 518 | 24 | | PK | 12-3 | 21-53-11 | D07960J | | 7 | | | | | D01302 | 18 | | | 278 |
| 519 | 24 | | PK | 14-0 | 21-53-11 | D04726J | | 47 | | | | | D01302 | 19 | | | 050-099, 150-199, 275-277, 280-299 |
| 519 | 24 | | PK | 13-4 | 21-53-11 | D04726J | | 47 | | | | | D01302 | 19 | | | 278 |
| 51A | 24 | | PK | 4-0 | 21-53-22 | D07960J | | 9 | | | | | TB0100Y | C039 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 51A | 24 | | PK | 3-4 | 21-53-22 | D07960J | | 9 | | | | | TB0100Y | C039 | BJ | | 278 |
| 51B | 24 | | PK | 6-0 | 21-53-22 | TB0100Y | | C039 | BJ | | | | D04726J | 56 | | | 050-099, 150-199, 275-277, 280-299 |
| 51B | 24 | | PK | 4-5 | 21-53-22 | TB0100Y | | C039 | BJ | | | | D04726J | 56 | | | 278 |
| 51C | 24 | | PK | 5-0 | 21-53-22 | TB0100Y | | C039 | BJ | | | | D04708J | 22 | | | 050-099, 150-199, 275-277, 280-299 |
| 51C | 24 | | PK | 4-3 | 21-53-22 | TB0100Y | | C039 | BJ | | | | D04708J | 22 | | | 278 |
| 51D | 24 | | PK | 5-0 | 21-53-22 | D07960J | | 10 | | | | | D04708J | 15 | | | 050-099, 150-199, 275-277, 280-299 |
| 51D | 24 | | PK | 3-6 | 21-53-22 | D07960J | | 10 | | | | | D04708J | 15 | | | 278 |
| 51E | 24 | | PK | 5-0 | 21-58-11 | TB0102Y | | C015 | BJ | | | | D04708J | 52 | | | 050-099, 150-199, 275-277, 280-299 |
| 51E | 24 | | PK | 4-4 | 21-58-11 | TB0102Y | | C015 | BJ | | | | D04708J | 52 | | | 278 |
| 51K | 24 | | PK | 4-0 | 21-58-14 | D07960J | | 14 | | | | | D04726J | 15 | | | 050-099, 150-199, 275-277, 280-299 |
| 51K | 24 | | PK | 3-8 | 21-58-14 | D07960J | | 14 | | | | | D04726J | 15 | | | 278 |
| 51N | 12 | | PA | 7-0 | 21-58-14 | D05934P | | 1 | | | | | D05910J | 1 | | | 050-099, 150-199, 275-277, 280-299 |
| 51N | 12 | | PA | 6-4 | 21-58-14 | D05934P | | 1 | | | | | D05910J | 1 | | | 278 |
| 51P | 12 | | PA | 7-0 | 21-58-14 | D05934P | | 8 | | | | | D05910J | 2 | | | 050-099, 150-199, 275-277, 280-299 |
| 51P | 12 | | PA | 6-4 | 21-58-14 | D05934P | | 8 | | | | | D05910J | 2 | | | 278 |
| 51R | 12 | | PA | 7-0 | 21-58-14 | D05934P | | 10 | | | | | D05910J | 3 | | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 29

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | | | |
| 51R | 12 | | PA | 6-4 | 21-58-14 | D05934P | | 10 | | | | | D05910J | | 3 | | | | 278 |
| 51U | 24 | | PK | 4-0 | 21-61-51 | D07960J | | 25 | | | | | TB0102X | C002 | | BJ | | | 050-099, 150-199, 275-277, 280-299 |
| 51U | 24 | | PK | 3-5 | 21-61-51 | D07960J | | 25 | | | | | TB0102X | C002 | | BJ | | | 278 |
| 51V | 24 | | PK | 5-0 | 21-61-51 | D07960J | | 26 | | | | | D05726J | | 22 | | | | 050-099, 150-199, 275-277, 280-299 |
| 51V | 24 | | PK | 3-4 | 21-61-51 | D07960J | | 26 | | | | | D05726J | | 22 | | | | 278 |
| 51W | 24 | | PK | 4-0 | 24-11-11 | D05400J | | 18 | | | | | TB0100Y | A034 | | BJ | | | 050-099, 150-199, 275-277, 280-299 |
| 51W | 24 | | PK | 3-9 | 24-11-11 | D05400J | | 18 | | | | | TB0100Y | A034 | | BJ | | | 278 |
| 51X | 24 | | PK | 6-0 | 24-11-11 | TB0100Y | | A034 | | BJ | | | D04778J | | 9 | | | | 050-099, 150-199, 275-277, 280-299 |
| 51X | 24 | | PK | 4-9 | 24-11-11 | TB0100Y | | A034 | | BJ | | | D04778J | | 9 | | | | 278 |
| 51Y | 24 | | PK | 6-0 | 24-11-11 | TB0100Y | | A034 | | BJ | | | D04778J | | 8 | | | | 050-099, 150-199, 275-277, 280-299 |
| 51Y | 24 | | PK | 4-9 | 24-11-11 | TB0100Y | | A034 | | BJ | | | D04778J | | 8 | | | | 278 |
| 51Z | 24 | | PK | 5-0 | 21-51-11 | TB0100X | | A001 | | BJ | | | D04644J | | 22 | | | | 050-099, 150-199, 275-277, 280-299 |
| 51Z | 24 | | PK | 4-3 | 21-51-11 | TB0100X | | A001 | | BJ | | | D04644J | | 22 | | | | 278 |
| 520 | 24 | | PK | 14-0 | 21-53-22 | D01302 | | 20 | | | | | D04726J | | 51 | | | | 050-099, 150-199, 275-277, 280-299 |
| 520 | 24 | | PK | 13-4 | 21-53-22 | D01302 | | 20 | | | | | D04726J | | 51 | | | | 278 |
| 521 | 20 | | PA | 6-0 | 24-51-72 | D04778J | | 48 | | | | | TB0100Y | C011 | | BJ | | | 050-099, 162-164, 276 |
| 522 | 24 | | PK | 14-0 | 21-53-22 | D01302 | | 22 | | | | | D04726J | | 53 | | | | 050-099, 150-199, 275-277, 280-299 |
| 522 | 24 | | PK | 13-4 | 21-53-22 | D01302 | | 22 | | | | | D04726J | | 53 | | | | 278 |
| 523 | 24 | | PK | 14-0 | 21-53-22 | D01302 | | 23 | | | | | D04726J | | 54 | | | | 050-099, 150-199, 275-277, 280-299 |
| 523 | 24 | | PK | 13-4 | 21-53-22 | D01302 | | 23 | | | | | D04726J | | 54 | | | | 278 |
| 524 | 24 | | PK | 14-0 | 21-53-22 | D01302 | | 24 | | | | | D04726J | | 55 | | | | 050-099, 150-199, 275-277, 280-299 |
| 524 | 24 | | PK | 13-4 | 21-53-22 | D01302 | | 24 | | | | | D04726J | | 55 | | | | 278 |
| 525 | 20 | | PA | 6-0 | 24-51-72 | D04778J | | 49 | | | | | TB0102X | B007 | | BJ | | | 050-099, 162-164, 276 |
| 526 | 20 | | PA | 8-0 | 33-13-16 | D12172 | | 1 | | | | | TB0064G | | 6 | | 2 | | 050-099, 155-199, 276-277, 280-299 |
| 526 | 20 | | PA | 7-0 | 33-13-16 | D12172 | | 1 | | | | | TB0064G | | 6 | | 2 | | 278 |
| 527 | 20 | | PA | 9-0 | 21-25-11 | D01302 | | 27 | | | | | GD00084 | | D.. | | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 527 | 20 | | PA | 7-2 | 21-25-11 | D01302 | | 27 | | | | | GD00084 | | D.. | | 2 | | 278 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 30
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 528 | 20 | | PA | 6-0 | 33-13-16 | D12172 | | 2 | | | | | GD00100 | A.. | 2 | | 050-099, 278 |
| 528 | 20 | | PA | 12-0 | 33-13-16 | D12172 | | 2 | | | | | GD00100 | A.. | 2 | | 155-199, 276-277, 280-299 |
| 529 | 24 | | PK | 14-0 | 21-51-11 | D01302 | | 29 | | | | | D04644J | 24 | | | 050-099 |
| 529 | 24 | | PK | 13-0 | 21-51-11 | D01302 | | 29 | | | | | D04644J | 24 | | | 150-199, 275-277, 280-299 |
| 529 | 24 | | PK | 13-1 | 21-51-11 | D01302 | | 29 | | | | | D04644J | 24 | | | 278 |
| 52A | 24 | | PK | 4-0 | 27-11-11 | D07964J | | 6 | | | | | D04714J | 21 | | | 050-099, 150-199, 275-277, 280-299 |
| 52A | 24 | | PK | 3-6 | 27-11-11 | D07964J | | 6 | | | | | D04714J | 21 | | | 278 |
| 52B | 24 | | PK | 4-0 | 27-18-11 | TB0100Y | | C033 | BJ | | | | D07964J | 22 | | | 050-099, 150-199, 275-277, 280-299 |
| 52B | 24 | | PK | 3-1 | 27-18-11 | TB0100Y | | C033 | BJ | | | | D07964J | 22 | | | 278 |
| 52C | 24 | | PK | 6-0 | 27-18-11 | TB0100Y | | A013 | BJ | | | | D04718J | 4 | | | 050-099, 150-199, 275-277, 280-299 |
| 52C | 24 | | PK | 4-7 | 27-18-11 | TB0100Y | | A013 | BJ | | | | D04718J | 4 | | | 278 |
| 52D | 24 | | PK | 6-0 | 27-18-11 | TB0100Y | | A013 | BJ | | | | D04718J | 1 | | | 050-099, 150-199, 275-277, 280-299 |
| 52D | 24 | | PK | 4-7 | 27-18-11 | TB0100Y | | A013 | BJ | | | | D04718J | 1 | | | 278 |
| 52E | 24 | | PK | 6-0 | 27-18-11 | TB0100Y | | C033 | BJ | | | | D04710J | 41 | | | 050-099, 150-199, 275-277, 280-299 |
| 52E | 24 | | PK | 4-9 | 27-18-11 | TB0100Y | | C033 | BJ | | | | D04710J | 41 | | | 278 |
| 52F | 24 | | PK | 6-0 | 27-18-11 | TB0100Y | | C033 | BJ | | | | D04710J | 44 | | | 050-099, 150-199, 275-277, 280-299 |
| 52F | 24 | | PK | 4-9 | 27-18-11 | TB0100Y | | C033 | BJ | | | | D04710J | 44 | | | 278 |
| 52G | 20 | | PA | 4-0 | 27-21-11 | D07964J | | 8 | | | | | D04714J | 22 | | | 050-099, 150-199, 275-277, 280-299 |
| 52G | 20 | | PA | 3-6 | 27-21-11 | D07964J | | 8 | | | | | D04714J | 22 | | | 278 |
| 52H | 24 | | PK | 5-0 | 27-28-11 | D07964J | | 9 | | | | | D04710J | 1 | | | 050-099, 150-199, 275-277, 280-299 |
| 52H | 24 | | PK | 3-8 | 27-28-11 | D07964J | | 9 | | | | | D04710J | 1 | | | 278 |
| 52J | 24 | | PK | 5-0 | 27-28-13 | D07964J | | 10 | | | | | D04710J | 4 | | | 050-099, 150-199, 275-277, 280-299 |
| 52J | 24 | | PK | 3-8 | 27-28-13 | D07964J | | 10 | | | | | D04710J | 4 | | | 278 |
| 52K | 24 | | PK | 5-0 | 27-38-11 | D07964J | | 11 | | | | | D04714J | 16 | | | 050-099, 150-199, 275-277, 280-299 |
| 52K | 24 | | PK | 3-6 | 27-38-11 | D07964J | | 11 | | | | | D04714J | 16 | | | 278 |
| 52L | 24 | | PK | 4-0 | 27-51-31 | D07964J | | 12 | | | | | D04718J | 8 | | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 31

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 52L | 24 | | PK | 3-6 | 27-51-31 | D07964J | | 12 | | | | D04718J | | 8 | | 278 |
| 52M | 22 | | PA | 4-0 | 27-51-51 | D07964J | | 13 | | | | D04714J | | 9 | | 050-099, 150-199, 275-277, 280-299 |
| 52M | 22 | | PA | 3-6 | 27-51-51 | D07964J | | 13 | | | | D04714J | | 9 | | 278 |
| 52N | 24 | | PK | 4-0 | 27-58-11 | TB0100Y | | A032 | BJ | | | D07964J | | 16 | | 050-099, 150-199, 275-277, 280-299 |
| 52N | 24 | | PK | 3-1 | 27-58-11 | TB0100Y | | A032 | BJ | | | D07964J | | 16 | | 278 |
| 52P | 24 | | PK | 5-0 | 27-58-11 | TB0100Y | | A032 | BJ | | | D04732J | | 28 | | 050-099, 150-199, 275-277, 280-299 |
| 52P | 24 | | PK | 4-3 | 27-58-11 | TB0100Y | | A032 | BJ | | | D04732J | | 28 | | 278 |
| 52R | 24 | | PK | 6-0 | 27-58-11 | TB0100Y | | A032 | BJ | | | D04714J | | 3 | | 050-099, 150-199, 275-277, 280-299 |
| 52R | 24 | | PK | 4-7 | 27-58-11 | TB0100Y | | A032 | BJ | | | D04714J | | 3 | | 278 |
| 52S | 24 | | PK | 4-0 | 27-58-11 | TB0100Y | | C032 | BJ | | | D07964J | | 17 | | 050-099, 150-199, 275-277, 280-299 |
| 52S | 24 | | PK | 3-1 | 27-58-11 | TB0100Y | | C032 | BJ | | | D07964J | | 17 | | 278 |
| 52T | 24 | | PK | 6-0 | 27-58-11 | TB0100Y | | C032 | BJ | | | D04714J | | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 52T | 24 | | PK | 4-7 | 27-58-11 | TB0100Y | | C032 | BJ | | | D04714J | | 2 | | 278 |
| 52U | 24 | | PK | 5-0 | 27-58-11 | TB0100Y | | C032 | BJ | | | D04732J | | 29 | | 050-099, 150-199, 275-277, 280-299 |
| 52U | 24 | | PK | 4-3 | 27-58-11 | TB0100Y | | C032 | BJ | | | D04732J | | 29 | | 278 |
| 52V | 24 | | PK | 4-0 | 27-58-11 | D07964J | | 18 | | | | D04714J | | 4 | | 050-099, 150-199, 275-277, 280-299 |
| 52V | 24 | | PK | 3-6 | 27-58-11 | D07964J | | 18 | | | | D04714J | | 4 | | 278 |
| 52W | 24 | | PK | 2-0 | 27-58-11 | D04714J | | 8 | | | | D04732J | | 30 | | 050-099, 150-199, 275-277, 280-299 |
| 52W | 24 | | PK | 1-10 | 27-58-11 | D04714J | | 8 | | | | D04732J | | 30 | | 278 |
| 52X | 24 | | PK | 2-0 | 27-58-11 | D04714J | | 7 | | | | D04732J | | 31 | | 050-099, 150-199, 275-277, 280-299 |
| 52X | 24 | | PK | 1-10 | 27-58-11 | D04714J | | 7 | | | | D04732J | | 31 | | 278 |
| 52Y | 24 | | PK | 2-0 | 27-58-11 | D04714J | | 6 | | | | D04732J | | 32 | | 050-099, 150-199, 275-277, 280-299 |
| 52Y | 24 | | PK | 1-10 | 27-58-11 | D04714J | | 6 | | | | D04732J | | 32 | | 278 |
| 52Z | 24 | | PK | 2-0 | 27-58-11 | D04714J | | 5 | | | | D04732J | | 33 | | 050-099, 150-199, 275-277, 280-299 |
| 52Z | 24 | | PK | 1-10 | 27-58-11 | D04714J | | 5 | | | | D04732J | | 33 | | 278 |
| 530 | 20 | | PA | 2-0 | 33-13-16 | TB0064G | | 4 | 2 | | | TB0064G | | 6 | 2 | 050-099, 155-199, 276-277, 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 32
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 530 | 20 | | PA | 0-7 | 33-13-16 | TB0064G | 4 | 2 | | TB0064G | 6 | 2 | | 278 | | |
| 531 | 20 | | PA | 9-0 | 21-53-22 | D01302 | 31 | | | GD00086 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 | | |
| 531 | 20 | | PA | 7-4 | 21-53-22 | D01302 | 31 | | | GD00086 | D.. | 2 | | 278 | | |
| 535 | 22 | | PA | 7-0 | 33-16-17 | D12172 | 3 | | | TB0070Z | 29 | BJ | | 050-099, 155-199, 276-277, 280-299 | | |
| 535 | 22 | | PA | 6-10 | 33-16-17 | D12172 | 3 | | | TB0070Z | 29 | BJ | | 278 | | |
| 536 | 22 | | PA | 7-0 | 33-16-17 | D12172 | 4 | | | TB0070Z | 30 | BJ | | 050-099, 155-199, 276-277, 280-299 | | |
| 536 | 22 | | PA | 6-10 | 33-16-17 | D12172 | 4 | | | TB0070Z | 30 | BJ | | 278 | | |
| 537 | 24 | | PK | 5-0 | 23-22-15 | TB0098X | D022 | BJ | | D04955J | 8 | | | 050-099 | | |
| 537 | 24 | | PK | 7-0 | 23-22-15 | TB0098X | D022 | BJ | | D04955J | 8 | | | 150-154 | | |
| 537 | 24 | | PK | 6-0 | 23-22-15 | TB0098X | D022 | BJ | | D04955J | 8 | | | 155-199, 275-277, 280-299 | | |
| 537 | 24 | | PK | 4-3 | 23-22-15 | TB0098X | D022 | BJ | | D04955J | 8 | | | 278 | | |
| 538 | 22 | | PQ AW | 13-0 | 28-22-31 | D01330 | 20 | | | TB0104X | B038 | BJ | | 050-099 | | |
| 538 | 22 | | PQ BU | 13-0 | 28-22-31 | D01330 | 20 | | | TB0104X | B038 | BJ | | 150-199, 275-299 | | |
| 538Z | | | AW | 0-0 | 28-22-31 | D01330 | DED | | | TB0104X | DED | | | 050-099 | | |
| 538Z | | | BU | 0-0 | 28-22-31 | D01330 | DED | | | TB0104X | DED | | | 150-199, 275-299 | | |
| 539 | 22 | | PQ AX | 13-0 | 28-22-31 | D01330 | 21 | | | TB0104X | C038 | BJ | | 050-099 | | |
| 539 | 22 | | PQ BV | 13-0 | 28-22-31 | D01330 | 21 | | | TB0104X | C038 | BJ | | 150-199, 275-299 | | |
| 539Z | | | AX | 0-0 | 28-22-31 | D01330 | DED | | | TB0104X | DED | | | 050-099 | | |
| 539Z | | | BV | 0-0 | 28-22-31 | D01330 | DED | | | TB0104X | DED | | | 150-199, 275-299 | | |
| 53A | 24 | | PK | 9-0 | 24-11-11 | D05848P | 1 | | | D04778J | 36 | | | 150-199 | | |
| 53B | 24 | | PK | 9-0 | 24-11-11 | D05848P | 2 | | | D04778J | 37 | | | 150-199 | | |
| 53E | 24 | | PK | 4-0 | 24-11-11 | D07962J | 16 | | | D04778J | 17 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 53E | 24 | | PK | 3-8 | 24-11-11 | D07962J | 16 | | | D04778J | 17 | | | 278 | | |
| 53F | 22 | | PA | 2-0 | 27-58-31 | D04732J | 8 | | | D04710J | 9 | | | ALL | | |
| 53G | 24 | | PV TT | 6-0 | 24-51-31 | D04778J | 16 | | | TB0106Y | A011 | BJ | | 050-099, 150-199, 275-277, 280-299 | | |
| 53G | 24 | | PV TT | 5-0 | 24-51-31 | D04778J | 16 | | | TB0106Y | A011 | BJ | | 278 | | |
| 53GZ | | | TT | 0-0 | 24-51-31 | D04778J | DED | | | TB0106Y | DED | | | ALL | | |
| 53H | 24 | | PV TU | 6-0 | 24-51-31 | D04778J | 40 | | | TB0106Y | C011 | BJ | | 050-099, 150-199, 275-277, 280-299 | | |
| 53H | 24 | | PV TU | 5-0 | 24-51-31 | D04778J | 40 | | | TB0106Y | C011 | BJ | | 278 | | |
| 53HZ | | | TU | 0-0 | 24-51-31 | D04778J | DED | | | TB0106Y | DED | | | ALL | | |
| 53J | 24 | | PK | 4-0 | 24-51-71 | D07962J | 20 | | | TB0100Y | C034 | BJ | | 050-099, 150-199, 275-277, 280-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 33

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 53J | 24 | | PK | | 3-1 | 24-51-71 | D07962J | 20 | | | TB0100Y | C034 | BJ | | 278 |
| 53K | 24 | | PK | | 9-0 | 24-51-71 | TB0100Y | C034 | BJ | | D06154P | 20 | | | 050-099, 150-199, 275-277, 280-299 |
| 53K | 24 | | PK | | 8-5 | 24-51-71 | TB0100Y | C034 | BJ | | D06154P | 20 | | | 278 |
| 53L | 24 | | PK | | 6-0 | 24-51-71 | TB0100Y | C034 | BJ | | D04778J | 46 | | | 050-099, 150-199, 275-277, 280-299 |
| 53L | 24 | | PK | | 4-9 | 24-51-71 | TB0100Y | C034 | BJ | | D04778J | 46 | | | 278 |
| 53M | 24 | | PK | | 4-0 | 27-81-31 | D07964J | 21 | | | D04718J | 10 | | | 050-099, 150-199, 275-277, 280-299 |
| 53M | 24 | | PK | | 3-6 | 27-81-31 | D07964J | 21 | | | D04718J | 10 | | | 278 |
| 53N | 22 | | PA | | 3-0 | 27-88-11 | D04710J | 19 | | | D04730J | 9 | | | 050-099, 150-199, 275-277, 280-299 |
| 53N | 22 | | PA | | 2-1 | 27-88-11 | D04710J | 19 | | | D04730J | 9 | | | 278 |
| 53P | 24 | | PK | | 6-0 | 24-51-71 | TB0100Y | C016 | BJ | | D04778J | 44 | | | 050-099, 150-199, 275-277, 280-299 |
| 53P | 24 | | PK | | 4-9 | 24-51-71 | TB0100Y | C016 | BJ | | D04778J | 44 | | | 278 |
| 53R | 20 | | PA | | 4-0 | 27-62-11 | D07964J | 20 | | | D04714J | 1 | | | 050-099, 150-199, 275-277, 280-299 |
| 53R | 20 | | PA | | 3-6 | 27-62-11 | D07964J | 20 | | | D04714J | 1 | | | 278 |
| 53S | 24 | | PV | RS | 6-0 | 29-11-31 | D04778J | 32 | | | TB0102X | D005 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 53S | 24 | | PV | RS | 4-9 | 29-11-31 | D04778J | 32 | | | TB0102X | D005 | BJ | | 278 |
| 53SZ | | | | RS | 0-0 | 29-11-31 | D04778J | DED | | | TB0102X | DED | | | ALL |
| 53T | 22 | | PA | | 7-0 | 29-21-32 | D10732 | 14 | | | D04990J | 23 | | | 050-099, 150-199, 275-277, 280-299 |
| 53T | 22 | | PA | | 6-2 | 29-21-32 | D10732 | 14 | | | D04990J | 23 | | | 278 |
| 53V | 22 | | PQ | TL | 6-0 | 27-13-11 | TB0100Y | A033 | BJ | | D04714J | 24 | | | 050-099, 150-199, 275-277, 280-299 |
| 53V | 22 | | PQ | TL | 4-7 | 27-13-11 | TB0100Y | A033 | BJ | | D04714J | 24 | | | 278 |
| 53VZ | | | | TL | 0-0 | 27-13-11 | TB0100Y | DED | | | D04714J | DED | | | ALL |
| 53W | 22 | | PQ | TK | 5-0 | 27-13-11 | TB0100Y | A033 | BJ | | D05402J | 5 | | | 050-099, 150-199, 275-277, 280-299 |
| 53W | 22 | | PQ | TK | 3-10 | 27-13-11 | TB0100Y | A033 | BJ | | D05402J | 5 | | | 278 |
| 53WZ | | | | TK | 0-0 | 27-13-11 | TB0100Y | DED | | | D05402J | DED | | | ALL |
| 540 | 22 | | PQ | AY | 13-0 | 28-22-31 | D01330 | 28 | | | TB0104Y | C036 | BJ | | 050-099 |
| 540 | 22 | | PQ | BW | 13-0 | 28-22-31 | D01330 | 28 | | | TB0104Y | C036 | BJ | | 150-199, 275-299 |
| 540Z | | | | AY | 0-0 | 28-22-31 | D01330 | DED | | | TB0104Y | DED | | | 050-099 |
| 540Z | | | | BW | 0-0 | 28-22-31 | D01330 | DED | | | TB0104Y | DED | | | 150-199, 275-299 |
| 541 | 22 | | PQ | BA | 14-0 | 28-22-31 | D01330 | 29 | | | D04714J | 54 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 34

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 541 | 22 | PQ | BX | 14-0 | 28-22-31 | D01330 | | 29 | | | | D04714J | 54 | | 150-199, 275-299 | |
| 541Z | | | BA | 0-0 | 28-22-31 | D01330 | | DED | | | | D04714J | DED | | 050-099 | |
| 541Z | | | BX | 0-0 | 28-22-31 | D01330 | | DED | | | | D04714J | DED | | 150-199, 275-299 | |
| 542 | 22 | PQ | BB | 14-0 | 28-22-31 | D01330 | | 7 | | | | D04714J | 55 | | 050-099 | |
| 542 | 22 | PQ | BY | 14-0 | 28-22-31 | D01330 | | 7 | | | | D04714J | 55 | | 150-199, 275-299 | |
| 542Z | | | BB | 0-0 | 28-22-31 | D01330 | | DED | | | | D04714J | DED | | 050-099 | |
| 542Z | | | BY | 0-0 | 28-22-31 | D01330 | | DED | | | | D04714J | DED | | 150-199, 275-299 | |
| 543 | 22 | PQ | BC | 7-0 | 28-22-31 | TB0104X | | D038 | BJ | | | D04714J | 56 | | 050-099 | |
| 543 | 22 | PQ | CD | 7-0 | 28-22-31 | TB0104X | | D038 | BJ | | | D04714J | 56 | | 150-199, 275-299 | |
| 543Z | | | BC | 0-0 | 28-22-31 | TB0104X | | DED | | | | D04714J | DED | | 050-099 | |
| 543Z | | | CD | 0-0 | 28-22-31 | TB0104X | | DED | | | | D04714J | DED | | 150-199, 275-299 | |
| 544 | 22 | PQ | BD | 7-0 | 28-22-31 | TB0104Y | | C036 | BJ | | | D04714J | 53 | | 050-099 | |
| 544 | 22 | PQ | CE | 7-0 | 28-22-31 | TB0104Y | | C036 | BJ | | | D04714J | 53 | | 150-199, 275-299 | |
| 544Z | | | BD | 0-0 | 28-22-31 | TB0104Y | | DED | | | | D04714J | DED | | 050-099 | |
| 544Z | | | CE | 0-0 | 28-22-31 | TB0104Y | | DED | | | | D04714J | DED | | 150-199, 275-299 | |
| 546 | 20 | UA | | 11-0 | 78-34-11 | D04710J | | | | GA | | GD04432 | S.. | 2 | 050-099, 150-156, 162-166 | |
| 546 | 20 | PA | | 11-0 | 78-34-11 | D04710J | | | | GA | | GD04432 | S.. | 2 | 157, 167-199, 277, 280-299 | |
| 546 | 20 | UA | | 11-0 | 78-34-11 | D04710J | | | | GA | | GD04430 | S.. | 2 | 275-276 | |
| 546 | 20 | PA | | 4-8 | 78-34-11 | D04710J | | | | GA | | GD04432 | S.. | 2 | 278 | |
| 54A | 24 | PK | | 6-0 | 24-22-11 | D04778J | | 12 | | | | TB0098X | B004 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 54A | 24 | PK | | 4-9 | 24-22-11 | D04778J | | 12 | | | | TB0098X | B004 | BJ | 278 | |
| 54D | 24 | PK | | 2-0 | 27-51-11 | D04732J | | 7 | | | | D04710J | 12 | | ALL | |
| 54H | 24 | PK | | 6-0 | SPARE | TB0100Y | | C027 | BJ | | | D05282J | 25 | | 152, 154, 156, 162, 166-199 | |
| 54J | 24 | PK | | 6-0 | SPARE | TB0100Y | | C027 | BJ | | | D05180J | 20 | | 152, 154, 156, 162, 166-199 | |
| 54N | 22 | PA | | 4-0 | 52-11-12 | D07962J | | 24 | | | | D04726J | 25 | | 050-099, 150-199 | |
| 54N | 20 | PA | | 4-0 | 52-11-12 | D07962J | | 24 | | | | D04726J | 25 | | 275-277, 280-299 | |
| 54N | 20 | PA | | 3-5 | 52-11-12 | D07962J | | 24 | | | | D04726J | 25 | | 278 | |
| 54R | 24 | PK | | 4-0 | 29-31-11 | D07966J | | 10 | | | | D04726J | 50 | | 050-099, 150-199, 275-277, 280-299 | |
| 54R | 24 | PK | | 3-6 | 29-31-11 | D07966J | | 10 | | | | D04726J | 50 | | 278 | |
| 54S | 24 | PV | TI | 4-0 | 29-31-11 | D07962J | | 10 | | | | D05732J | 1 | | 050-099, 150-199, 275-277, 280-299 | |
| 54S | 24 | PV | TI | 3-1 | 29-31-11 | D07962J | | 10 | | | | D05732J | 1 | | 278 | |
| 54SZ | | | TI | 0-0 | 29-31-11 | D07962J | | DED | | | | D05732J | DED | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 35

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 55A | 24 | | PK | 4-0 | 27-51-61 | D07964J | | 15 | | | D04714J | | 14 | | 050-099, 150-199, 275-277, 280-299 278 | |
| 55A | 24 | | PK | 3-6 | 27-51-61 | D07964J | | 15 | | | D04714J | | 14 | | 278 | |
| 55B | 24 | | PK | 4-0 | 27-51-61 | D07964J | | 14 | | | D04714J | | 15 | | 050-099, 150-199, 275-277, 280-299 278 | |
| 55B | 24 | | PK | 3-6 | 27-51-61 | D07964J | | 14 | | | D04714J | | 15 | | 278 | |
| 55C | 24 | | PK | 4-0 | 27-58-21 | D07964J | | 19 | | | D04710J | | 48 | | 050-099, 150-199, 275-277, 280-299 278 | |
| 55C | 24 | | PK | 3-8 | 27-58-21 | D07964J | | 19 | | | D04710J | | 48 | | 278 | |
| 55P | 22 | | PA | 5-0 | 29-11-11 | D07966J | | 1 | | | TB0098Y | A013 | BJ | | 050-099, 150-199, 275-277, 280-299 278 | |
| 55P | 22 | | PA | 3-3 | 29-11-11 | D07966J | | 1 | | | TB0098Y | A013 | BJ | | 278 | |
| 55R | 22 | | PA | 6-0 | 29-11-11 | D04720J | | 8 | | | TB0098Y | C013 | BJ | | 050-099, 150-199, 275-277, 280-299 278 | |
| 55R | 22 | | PA | 3-9 | 29-11-11 | D04720J | | 8 | | | TB0098Y | C013 | BJ | | 278 | |
| 55T | 22 | | PQ TF | 6-0 | 29-32-11 | D04778J | | 33 | | | TB0100Y | A029 | BJ | | 050-099, 150-199, 275-277, 280-299 278 | |
| 55T | 22 | | PQ TF | 4-9 | 29-32-11 | D04778J | | 33 | | | TB0100Y | A029 | BJ | | 278 | |
| 55TZ | | | | 0-0 | 29-32-11 | D04778J | | DED | | | TB0100Y | | DED | | ALL | |
| 55U | 22 | | PQ TC | 5-0 | 29-32-11 | D05402J | | 12 | | | TB0100Y | A029 | BJ | | 050-099, 150-199, 275-277, 280-299 278 | |
| 55U | 22 | | PQ TC | 3-10 | 29-32-11 | D05402J | | 12 | | | TB0100Y | A029 | BJ | | 278 | |
| 55UZ | | | | 0-0 | 29-32-11 | D05402J | | DED | | | TB0100Y | | DED | | ALL | |
| 55V | 22 | | PQ TE | 6-0 | 29-32-11 | D04778J | | 34 | | | TB0100Y | C029 | BJ | | 050-099, 150-199, 275-277, 280-299 278 | |
| 55V | 22 | | PQ TE | 4-9 | 29-32-11 | D04778J | | 34 | | | TB0100Y | C029 | BJ | | 278 | |
| 55VZ | | | | 0-0 | 29-32-11 | D04778J | | DED | | | TB0100Y | | DED | | ALL | |
| 55W | 22 | | PQ TD | 5-0 | 29-32-11 | D05402J | | 13 | | | TB0100Y | C029 | BJ | | 050-099, 150-199, 275-277, 280-299 278 | |
| 55W | 22 | | PQ TD | 3-10 | 29-32-11 | D05402J | | 13 | | | TB0100Y | C029 | BJ | | 278 | |
| 55WZ | | | | 0-0 | 29-32-11 | D05402J | | DED | | | TB0100Y | | DED | | ALL | |
| 55Y | 22 | | PA | 5-0 | 28-41-13 | TB0100Y | | A012 | BJ | | D04718J | | 5 | | 050-099, 150-199, 275-277, 280-299 278 | |
| 55Y | 22 | | PA | 4-7 | 28-41-13 | TB0100Y | | A012 | BJ | | D04718J | | 5 | | 278 | |
| 55Z | 22 | | PA | 4-0 | 28-41-13 | TB0100Y | | A012 | BJ | | D05400J | | 4 | | 050-099, 150-156, 162-166, 275-276 278 | |
| 561 | 18 | | PA | 7-0 | 33-13-16 | D00848 | | 1 | DK | | TB0068G | | 5 | 2 | 050-099, 150-199, 275-277, 280-299 278 | |
| 561 | 18 | | PA | 6-7 | 33-13-16 | D00848 | | 1 | DK | | TB0068G | | 5 | 2 | 278 | |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 36
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 562 | 18 | | PA | 7-0 | 33-13-16 | D00848 | | 2 | DK | | | | GD00100 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 562 | 18 | | PA | 5-3 | 33-13-16 | D00848 | | 2 | DK | | | | GD00100 | A.. | 2 | | 278 |
| 564 | 22 | | PA | 13-0 | 74-31-11 | D04732J | | 6 | | | | | D00848 | | 4 | | 050-099, 150-199, 275-277, 280-299 |
| 564 | 22 | | PA | 12-1 | 74-31-11 | D04732J | | 6 | | | | | D00848 | | 4 | | 278 |
| 568 | 24 | | PK | 17-0 | 80-11-11 | D00848 | | 8 | | | | | D06152P | | 21 | | 050-099, 150-199, 275-277, 280-299 |
| 568 | 24 | | PK | 15-10 | 80-11-11 | D00848 | | 8 | | | | | D06152P | | 21 | | 278 |
| 56A | 24 | | PK | 4-0 | 30-41-11 | D07962J | | 28 | | | | | TB0100Y | C014 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 56A | 24 | | PK | 3-1 | 30-41-11 | D07962J | | 28 | | | | | TB0100Y | C014 | BJ | | 278 |
| 56B | 24 | | PK | 4-0 | 30-41-11 | D05064J | | 1 | | | | | TB0100Y | C014 | BJ | | ALL |
| 56C | 22 | | PA | 3-0 | 30-31-11 | D05726J | | 52 | | | | | D05064J | | 7 | | 050-099, 150-199, 275-277, 280-299 |
| 56C | 22 | | PA | 2-9 | 30-31-11 | D05726J | | 52 | | | | | D05064J | | 7 | | 278 |
| 56D | 24 | | PK | 7-0 | 30-21-11 | D04968P | | 7 | | | | | TB0070Y | A018 | BJ | | 275-277, 280-299 |
| 56D | 24 | | PK | 6-5 | 30-21-11 | D04968P | | 7 | | | | | TB0070Y | A018 | BJ | | 278 |
| 56E | 24 | | PK | 13-0 | 30-21-11 | D05402J | | 14 | | | | | TB0070Y | A017 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 56E | 24 | | PK | 11-6 | 30-21-11 | D05402J | | 14 | | | | | TB0070Y | A017 | BJ | | 278 |
| 56F | 24 | | PK | 3-0 | 30-31-11 | D07962J | | 27 | | | | | D05726J | | 42 | | 050-099, 150-199, 275-277, 280-299 |
| 56F | 24 | | PK | 3-1 | 30-31-11 | D07962J | | 27 | | | | | D05726J | | 42 | | 278 |
| 56G | 22 | | PA | 8-0 | 30-31-11 | D05934P | | 11 | | | | | D05064J | | 5 | | 050-099, 150-199, 275-277, 280-299 |
| 56G | 22 | | PA | 7-6 | 30-31-11 | D05934P | | 11 | | | | | D05064J | | 5 | | 278 |
| 56H | 22 | | PA | 7-0 | 30-31-11 | D05934P | | 12 | | | | | D05726J | | 45 | | 050-099, 150-199, 275-277, 280-299 |
| 56H | 22 | | PA | 6-8 | 30-31-11 | D05934P | | 12 | | | | | D05726J | | 45 | | 278 |
| 56K | 22 | | PA | 4-0 | 30-32-11 | D04708J | | 43 | | | | | D04718J | | 12 | | 050-099, 150-199, 275-277, 280-299 |
| 56K | 22 | | PA | 3-5 | 30-32-11 | D04708J | | 43 | | | | | D04718J | | 12 | | 278 |
| 56L | 22 | | PA | 7-0 | 30-32-11 | D05934P | | 15 | | | | | D04708J | | 61 | | 050-099, 150-199, 275-277, 280-299 |
| 56L | 22 | | PA | 6-2 | 30-32-11 | D05934P | | 15 | | | | | D04708J | | 61 | | 278 |
| 56M | 22 | | PA | 6-0 | 30-33-11 | D05934P | | 17 | | | | | D05282J | | 13 | | ALL |
| 56N | 22 | | PA | 7-0 | 30-34-11 | D05934P | | 18 | | | | | D04708J | | 10 | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 37

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|---------|------|--------|---------------------------------------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 56N | 22 | | PA | | 6-2 | 30-34-11 | D05934P | | | | D04708J | | | | 278 | |
| 56V | 22 | | PQ | SO | 7-0 | 30-43-11 | D04966P | | | 1 | TB0066X | D005 | BJ | | 050-099, 150-199, 275-277, 280-299 | |
| 56V | 22 | | PQ | SO | 6-9 | 30-43-11 | D04966P | | | 1 | TB0066X | D005 | BJ | | 278 | |
| 56VZ | | | | SO | 0-0 | 30-43-11 | D04966P | | | DED | TB0066X | DED | | | ALL | |
| 56W | 24 | | PK | | 13-0 | 30-21-11 | D05402J | | | 15 | TB0070Y | A018 | BJ | | 275-277, 280-299 | |
| 56W | 24 | | PK | | 11-6 | 30-21-11 | D05402J | | | 15 | TB0070Y | A018 | BJ | | 278 | |
| 570 | 22 | | PA | | 7-0 | 74-31-11 | D05000P | | | 16 | D00848 | | | 10 | 050-099, 150-199, 275-277, 280-299 | |
| 570 | 22 | | PA | | 6-4 | 74-31-11 | D05000P | | | 16 | D00848 | | | 10 | 278 | |
| 571 | 22 | | PA | | 12-0 | SPARE | TB0100Y | | | CAP | Y | D00848 | | CAP | Y | 050-099, 150-199, 275-277, 280-299 |
| 571 | 22 | | PA | | 11-7 | SPARE | TB0100Y | | | CAP | Y | D00848 | | CAP | Y | 278 |
| 572 | 22 | | PA | | 12-0 | 74-31-11 | TB0100Y | | | A026 | BJ | D00848 | | 12 | 050-099, 150-199, 275-277, 280-299 | |
| 572 | 22 | | PA | | 11-7 | 74-31-11 | TB0100Y | | | A026 | BJ | D00848 | | 12 | 278 | |
| 57A | 24 | | PK | | 4-0 | 32-09-11 | D07966J | | | 18 | D04726J | | | 19 | 050-099, 150-199, 275-277, 280-299 | |
| 57A | 24 | | PK | | 3-6 | 32-09-11 | D07966J | | | 18 | D04726J | | | 19 | 278 | |
| 57B | 18 | | PA | | 4-0 | 32-35-11 | D07966J | | | 19 | DL | D04720J | | 3 | DK | 050-099, 150-199, 275-277, 280-299 |
| 57B | 18 | | PA | | 2-9 | 32-35-11 | D07966J | | | 19 | DL | D04720J | | 3 | DK | 278 |
| 57K | 24 | | PK | | 4-0 | 32-42-11 | D07966J | | | 21 | | TB0102D | | A018 | 2 | 050-099, 150-199, 275-277, 280-299 |
| 57K | 24 | | PK | | 3-3 | 32-42-11 | D07966J | | | 21 | | TB0102D | | A018 | 2 | 278 |
| 57L | 24 | | PK | | 4-0 | 32-42-11 | D07966J | | | 22 | | D04726J | | 8 | 050-099, 150-199, 275-277, 280-299 | |
| 57L | 24 | | PK | | 3-6 | 32-42-11 | D07966J | | | 22 | | D04726J | | 8 | 278 | |
| 57M | 24 | | PK | | 6-0 | 32-42-12 | D04714J | | | 42 | | D05652J | | 6 | 050-099, 150-199, 275-277, 280-299 | |
| 57M | 24 | | PK | | 3-8 | 32-42-12 | D04714J | | | 42 | | D05652J | | 6 | 278 | |
| 57N | 24 | | PK | | 6-0 | 32-42-12 | D04714J | | | 43 | | D05652J | | 7 | 050-099, 150-199, 275-277, 280-299 | |
| 57N | 24 | | PK | | 3-8 | 32-42-12 | D04714J | | | 43 | | D05652J | | 7 | 278 | |
| 57P | 24 | | PK | | 6-0 | 32-42-12 | D04714J | | | 44 | | D05652J | | 4 | 050-099, 150-199, 275-277, 280-299 | |
| 57P | 24 | | PK | | 3-8 | 32-42-12 | D04714J | | | 44 | | D05652J | | 4 | 278 | |
| 57R | 24 | | PK | | 6-0 | 32-42-12 | D04714J | | | 41 | | D05652J | | 5 | 050-099, 150-199, 275-277, 280-299 | |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 38
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 57R | 24 | | PK | 3-8 | 32-42-12 | D04714J | | 41 | | | | | D05652J | 5 | | | 278 |
| 57S | 24 | | PK | 4-0 | 32-46-11 | D07966J | | 23 | | | | | D04644J | 40 | | | 050-099 |
| 57S | 24 | | PK | 5-0 | 32-46-11 | D07966J | | 23 | | | | | D04644J | 40 | | | 150-199, 275-277, 280-299 |
| 57S | 24 | | PK | 3-3 | 32-46-11 | D07966J | | 23 | | | | | D04644J | 40 | | | 278 |
| 57T | 22 | | PA | 4-0 | 32-46-11 | D04732J | | 19 | | | | | D04644J | 41 | | | 050-099, 150-199, 275-277, 280-299 |
| 57T | 22 | | PA | 3-0 | 32-46-11 | D04732J | | 19 | | | | | D04644J | 41 | | | 278 |
| 584 | 18 | | PA | 5-0 | 30-42-11 | D00832 | | 4 | | | | | D04966P | 10 | | | 050-099, 150-199, 275-277, 280-299 |
| 584 | 18 | | PA | 4-11 | 30-42-11 | D00832 | | 4 | | | | | D04966P | 10 | | | 278 |
| 587 | 18 | | PA | 8-0 | 30-42-11 | D00832 | | 7 | | | | | D05000P | 21 | | | 050-099, 150-199, 275-277, 280-299 |
| 587 | 18 | | PA | 7-6 | 30-42-11 | D00832 | | 7 | | | | | D05000P | 21 | | | 278 |
| 588 | 22 | | PA | 8-0 | 30-43-11 | D05000P | | 33 | | | | | D00832 | 8 | | | 050-099, 150-199, 275-277, 280-299 |
| 588 | 22 | | PA | 7-6 | 30-43-11 | D05000P | | 33 | | | | | D00832 | 8 | | | 278 |
| 589 | 22 | | PA | 8-0 | 30-43-11 | D00832 | | 9 | | | | | TB0070X | A005 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 589 | 22 | | PA | 7-10 | 30-43-11 | D00832 | | 9 | | | | | TB0070X | A005 | BJ | | 278 |
| 58C | 20 | | PA | 8-0 | 36-21-11 | D03892 | | 7 | | | | | GD00084 | S.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 58C | 20 | | PA | 7-6 | 36-21-11 | D03892 | | 7 | | | | | GD00084 | S.. | 2 | | 278 |
| 58D | 20 | | PA | 8-0 | 36-21-11 | D03892 | | 9 | | | | | GD00084 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 58D | 20 | | PA | 7-6 | 36-21-11 | D03892 | | 9 | | | | | GD00084 | A.. | 2 | | 278 |
| 58E | 24 | | PK | 12-0 | 36-21-11 | D03892 | | 8 | | | | | D07962J | 7 | | | 050-099, 150-199, 275-277, 280-299 |
| 58E | 24 | | PK | 12-4 | 36-21-11 | D03892 | | 8 | | | | | D07962J | 7 | | | 278 |
| 58K | 20 | | PA | 5-0 | 33-42-21 | D05000P | | 27 | | | | | TB0070X | D003 | BJ | | 050-099 |
| 58K | 18 | | PA | 5-0 | 33-42-21 | D05000P | | 27 | DL | | | | TB0070F | C007 | 2 | | 150-199, 275-277, 280-299 |
| 58K | 18 | | PA | 3-6 | 33-42-21 | D05000P | | 27 | DL | | | | TB0070F | C007 | 2 | | 278 |
| 58L | 24 | | PK | 7-0 | 33-42-21 | D04968P | | 10 | | | | | TB0070X | D001 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 58L | 24 | | PK | 6-5 | 33-42-21 | D04968P | | 10 | | | | | TB0070X | D001 | BJ | | 278 |
| 58M | 20 | | PA | 7-0 | 33-42-21 | D04968P | | 3 | | | | | TB0070X | D002 | BJ | | 050-099 |
| 58M | 18 | | PA | 7-0 | 33-42-21 | D04968P | | 3 | DK | | | | TB0070F | A007 | 2 | | 150-199, 275-277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 39

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 58M | 18 | | PA | | 6-5 | 33-42-21 | D04968P | 3 | DK | | TB0070F | A007 | 2 | | 278 |
| 58N | 24 | | PK | | 5-0 | 33-42-11 | D05000P | 26 | | | TB0070Y | C015 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 58N | 24 | | PK | | 3-6 | 33-42-11 | D05000P | 26 | | | TB0070Y | C015 | BJ | | 278 |
| 58P | 16 | | PA | | 5-0 | 33-42-11 | D07970J | 7 | FL | | D04644J | 20 | FM | | 050-099, 150-199, 275-277, 280-299 |
| 58P | 16 | | PA | | 3-7 | 33-42-11 | D07970J | 7 | FL | | D04644J | 20 | FM | | 278 |
| 58R | 16 | | PA | | 5-0 | 33-42-11 | D07970J | 8 | FL | | D04644J | 58 | FM | | 050-099, 150-199, 275-277, 280-299 |
| 58R | 16 | | PA | | 3-7 | 33-42-11 | D07970J | 8 | FL | | D04644J | 58 | FM | | 278 |
| 590 | 18 | | PA | | 6-0 | 30-42-11 | D00832 | 10 | | | D04966P | 7 | | | 050-099, 150-199, 275-277, 280-299 |
| 590 | 18 | | PA | | 4-11 | 30-42-11 | D00832 | 10 | | | D04966P | 7 | | | 278 |
| 59A | 22 | | PA | | 13-0 | SPARE | D01678 | 2 | | | TB0106X | B003 | BJ | | 150-199, 275-277, 280-299 |
| 59A | 22 | | PA | | 11-10 | SPARE | D01678 | 2 | | | TB0106X | B003 | BJ | | 278 |
| 59B | 18 | | PA | | 5-0 | 26-13-11 | TB0102F | A011 | 2 | | D05180J | 35 | DK | | 050-099, 150-199 |
| 59D | 16 | | PA | | 5-0 | 33-26-21 | D07968J | 9 | FL | | D05180J | 1 | FM | | 050-099, 150-199, 275-277, 280-299 |
| 59D | 16 | | PA | | 4-1 | 33-26-21 | D07968J | 9 | FL | | D05180J | 1 | FM | | 278 |
| 59E | 22 | | PA | | 5-0 | 33-26-11 | D07968J | 8 | | | D05180J | 7 | | | 050-099, 150-199, 275-277, 280-299 |
| 59E | 22 | | PA | | 4-1 | 33-26-11 | D07968J | 8 | | | D05180J | 7 | | | 278 |
| 59F | 24 | | PK | | 5-0 | 33-24-11 | D07970J | 6 | | | D05180J | 17 | | | 050-099, 150-199, 275-277, 280-299 |
| 59F | 24 | | PK | | 4-3 | 33-24-11 | D07970J | 6 | | | D05180J | 17 | | | 278 |
| 59H | 22 | | PA | | 5-0 | 33-25-11 | TB0102X | A006 | BJ | | D05180J | 9 | | | 050-099, 150-199, 275-277, 280-299 |
| 59H | 22 | | PA | | 4-11 | 33-25-11 | TB0102X | A006 | BJ | | D05180J | 9 | | | 278 |
| 59K | 24 | | PK | | 8-0 | 33-11-11 | D07968J | 1 | | | D06152P | 1 | | | 050-099, 150-199, 275-277, 280-299 |
| 59K | 24 | | PK | | 7-8 | 33-11-11 | D07968J | 1 | | | D06152P | 1 | | | 278 |
| 59N | 24 | | PK | | 5-0 | 33-13-11 | D07968J | 15 | | | D04990J | 12 | | | 050-099, 150-199, 275-277, 280-299 |
| 59N | 24 | | PK | | 3-10 | 33-13-11 | D07968J | 15 | | | D04990J | 12 | | | 278 |
| 59P | 22 | | PA | | 4-0 | 33-13-18 | D05282J | 17 | | | D07970J | 15 | | | 050-099, 150-199, 275-277, 280-299 |
| 59P | 22 | | PA | | 3-10 | 33-13-18 | D05282J | 17 | | | D07970J | 15 | | | 278 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 40
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 59R | 24 | | PK | 5-0 | 33-14-21 | D04990J | | 11 | | | | | D07968J | 14 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 59R | 24 | | PK | 3-10 | 33-14-21 | D04990J | | 11 | | | | | D07968J | 14 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 59S | 24 | | PK | 6-0 | 33-14-31 | D04990J | | 13 | | | | | TB0100Z | 19 | BJ | | 050-099, 150-199, 275-277, 280-299 278 |
| 59S | 24 | | PK | 4-7 | 33-14-31 | D04990J | | 13 | | | | | TB0100Z | 19 | BJ | | 050-099, 150-199, 275-277, 280-299 278 |
| 59T | 24 | | PK | 6-0 | 33-14-31 | D04990J | | 14 | | | | | TB0100Z | 19 | BJ | | 050-099, 150-199, 275-277, 280-299 278 |
| 59T | 24 | | PK | 4-7 | 33-14-31 | D04990J | | 14 | | | | | TB0100Z | 19 | BJ | | 050-099, 150-199, 275-277, 280-299 278 |
| 59V | 24 | | PK | 8-0 | 33-16-11 | D07970J | | 9 | | | | | D06152P | 6 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 59V | 24 | | PK | 7-10 | 33-16-11 | D07970J | | 9 | | | | | D06152P | 6 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 59W | 22 | | PA | 5-0 | 33-16-12 | D07968J | | 2 | | | | | D04990J | 1 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 59W | 22 | | PA | 3-10 | 33-16-12 | D07968J | | 2 | | | | | D04990J | 1 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 59X | 22 | | PQ SH | 5-0 | 33-16-12 | D07968J | | 3 | | | | | D04990J | 2 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 59X | 22 | | PQ SH | 3-10 | 33-16-12 | D07968J | | 3 | | | | | D04990J | 2 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 59XZ | | | SH | 0-0 | 33-16-12 | D07968J | | DED | | | | | D04990J | DED | | | ALL |
| 59Y | 22 | | PQ SI | 5-0 | 33-16-12 | D07970J | | 2 | | | | | TB0098Y | A033 | BJ | | 050-099, 150-199, 275-277, 280-299 278 |
| 59Y | 22 | | PQ SI | 3-7 | 33-16-12 | D07970J | | 2 | | | | | TB0098Y | A033 | BJ | | 050-099, 150-199, 275-277, 280-299 278 |
| 59YZ | | | SI | 0-0 | 33-16-12 | D07970J | | DED | | | | | TB0098Y | DED | | | ALL |
| 59Z | 22 | | PQ SJ | 6-0 | 33-16-12 | D05282J | | 1 | | | | | TB0098Y | A033 | BJ | | 050-099, 150-199, 275-277, 280-299 278 |
| 59Z | 22 | | PQ SJ | 4-6 | 33-16-12 | D05282J | | 1 | | | | | TB0098Y | A033 | BJ | | 050-099, 150-199, 275-277, 280-299 278 |
| 59ZZ | | | SJ | 0-0 | 33-16-12 | D05282J | | DED | | | | | TB0098Y | DED | | | ALL |
| 603 | 22 | | PA | 8-0 | 33-16-17 | TB0070Z | | 29 | BJ | | | | D01330 | 3 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 603 | 22 | | PA | 7-6 | 33-16-17 | TB0070Z | | 29 | BJ | | | | D01330 | 3 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 604 | 22 | | PA | 8-0 | 33-16-17 | TB0070Z | | 30 | BJ | | | | D01330 | 4 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 604 | 22 | | PA | 7-6 | 33-16-17 | TB0070Z | | 30 | BJ | | | | D01330 | 4 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 605 | 22 | | PA | 14-0 | 28-42-11 | D04708J | | 5 | | | | | D01330 | 5 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 605 | 22 | | PA | 7-6 | 33-16-17 | TB0070Z | | 30 | BJ | | | | D01330 | 4 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 606 | 22 | | PA | 13-1 | 28-42-11 | D04708J | | 5 | | | | | D01330 | 5 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 606 | 22 | | PA | 14-0 | 28-42-11 | D04708J | | 1 | | | | | D01330 | 6 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 606 | 22 | | PA | 13-1 | 28-42-11 | D04708J | | 1 | | | | | D01330 | 6 | | | 050-099, 150-199, 275-277, 280-299 278 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 41

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 608 | 24 | | PK | | 13-0 | 28-42-31 | TB0102X | C005 | BJ | | D01330 | | 8 | | 050-099, 150-199, 275-277, 280-299 |
| 608 | 24 | | PK | | 12-7 | 28-42-31 | TB0102X | C005 | BJ | | D01330 | | 8 | | 278 |
| 60A | 22 | | PQ | RW | 16-0 | 33-16-12 | D06154P | | 2 | | TB0070Y | A031 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 60A | 22 | | PQ | RW | 15-7 | 33-16-12 | D06154P | | 2 | | TB0070Y | A031 | BJ | | 278 |
| 60AZ | | | | RW | 0-0 | 33-16-12 | D06154P | DED | | | TB0070Y | DED | | | ALL |
| 60B | 22 | | PQ | SF | 9-0 | 33-16-12 | D06154P | | 3 | | TB0098Y | A033 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 60B | 22 | | PQ | SF | 8-5 | 33-16-12 | D06154P | | 3 | | TB0098Y | A033 | BJ | | 278 |
| 60BZ | | | | SF | 0-0 | 33-16-12 | D06154P | DED | | | TB0098Y | DED | | | ALL |
| 60C | 22 | | PQ | SG | 16-0 | 33-16-12 | D06154P | | 4 | | TB0070Y | C031 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 60C | 22 | | PQ | SG | 15-7 | 33-16-12 | D06154P | | 4 | | TB0070Y | C031 | BJ | | 278 |
| 60CZ | | | | SG | 0-0 | 33-16-12 | D06154P | DED | | | TB0070Y | DED | | | ALL |
| 60D | 22 | | PA | | 16-0 | 33-16-12 | D06152P | | 2 | | TB0070Z | | 33 | BJ | 050-099, 150-199, 275-277, 280-299 |
| 60D | 22 | | PA | | 15-8 | 33-16-12 | D06152P | | 2 | | TB0070Z | | 33 | BJ | 278 |
| 60F | 22 | | PA | | 9-0 | 33-16-12 | D06152P | | 4 | | TB0098Y | C033 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 60F | 22 | | PA | | 8-7 | 33-16-12 | D06152P | | 4 | | TB0098Y | C033 | BJ | | 278 |
| 60G | 22 | | PA | | 16-0 | 33-16-12 | D06152P | | 5 | | TB0070Z | | 34 | BJ | 050-099, 150-199, 275-277, 280-299 |
| 60G | 22 | | PA | | 15-8 | 33-16-12 | D06152P | | 5 | | TB0070Z | | 34 | BJ | 278 |
| 60H | 22 | | PA | | 16-0 | 33-16-17 | D06152P | | 11 | | TB0070Y | A036 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 60H | 22 | | PA | | 15-8 | 33-16-17 | D06152P | | 11 | | TB0070Y | A036 | BJ | | 278 |
| 60J | 22 | | PA | | 16-0 | 33-16-17 | D06152P | | 12 | | TB0070Y | C036 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 60J | 22 | | PA | | 15-8 | 33-16-17 | D06152P | | 12 | | TB0070Y | C036 | BJ | | 278 |
| 60K | 22 | | PA | | 9-0 | 33-16-22 | D06152P | | 13 | | TB0098Y | A035 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 60K | 22 | | PA | | 8-7 | 33-16-22 | D06152P | | 13 | | TB0098Y | A035 | BJ | | 278 |
| 60L | 22 | | PA | | 16-0 | 33-16-22 | D06152P | | 14 | | TB0070Z | | 29 | BJ | 050-099, 150-199, 275-277, 280-299 |
| 60L | 22 | | PA | | 15-8 | 33-16-22 | D06152P | | 14 | | TB0070Z | | 29 | BJ | 278 |
| 60M | 22 | | PQ | SD | 9-0 | 33-16-22 | D06154P | | 13 | | TB0098Y | C035 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 60M | 22 | | PQ | SD | 8-5 | 33-16-22 | D06154P | | 13 | | TB0098Y | C035 | BJ | | 278 |

WIRE LIST

D280T132

91-21-11
Section W0060
Page 42
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 60MZ | | | SD | 0-0 | 33-16-22 | D06154P | DED | | | | | | TB0098Y | DED | | | ALL |
| 60R | 22 | PQ | SE | 9-0 | 33-16-22 | D06154P | 16 | | | | | | TB0098Z | 37 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 60R | 22 | PQ | SE | 8-5 | 33-16-22 | D06154P | 16 | | | | | | TB0098Z | 37 | BJ | | 278 |
| 60RZ | | | SE | 0-0 | 33-16-22 | D06154P | DED | | | | | | TB0098Z | DED | | | ALL |
| 60S | 22 | PA | | 9-0 | 33-16-22 | D06152P | 15 | | | | | | TB0098Z | 38 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 60S | 22 | PA | | 8-7 | 33-16-22 | D06152P | 15 | | | | | | TB0098Z | 38 | BJ | | 278 |
| 60T | 22 | PA | | 16-0 | 33-16-22 | D06152P | 16 | | | | | | TB0070Z | 30 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 60T | 22 | PA | | 15-8 | 33-16-22 | D06152P | 16 | | | | | | TB0070Z | 30 | BJ | | 278 |
| 60W | 22 | PA | | 11-0 | 33-16-22 | TB0098Z | 38 | BJ | | | | | TB0070Y | C035 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 60W | 22 | PA | | 11-5 | 33-16-22 | TB0098Z | 38 | BJ | | | | | TB0070Y | C035 | BJ | | 278 |
| 610 | 24 | PK | | 8-0 | 28-22-11 | D01330 | 10 | | | | | | D05000P | 37 | | | 050-099, 150-199, 275-277, 280-299 |
| 610 | 24 | PK | | 7-3 | 28-22-11 | D01330 | 10 | | | | | | D05000P | 37 | | | 278 |
| 611 | 24 | PK | | 14-0 | 28-22-11 | D01330 | 11 | | | | | | D04708J | 3 | | | 050-099, 150-199, 275-277, 280-299 |
| 611 | 24 | PK | | 13-1 | 28-22-11 | D01330 | 11 | | | | | | D04708J | 3 | | | 278 |
| 612 | 24 | PK | | 14-0 | 28-22-11 | D01330 | 12 | | | | | | D04708J | 4 | | | 050-099, 150-199, 275-277, 280-299 |
| 612 | 24 | PK | | 13-1 | 28-22-11 | D01330 | 12 | | | | | | D04708J | 4 | | | 278 |
| 613 | 24 | PK | | 8-0 | 28-22-12 | TB0070Y | A021 | BJ | | | | | D01330 | 13 | | | 050-099 |
| 613 | 24 | PK | | 8-0 | 28-22-12 | D01330 | 13 | | | | | | D05000P | 38 | | | 150-154, 275 |
| 613 | 24 | PK | | 8-0 | 28-22-12 | D01330 | 13 | | | | | | TB0070Y | A021 | BJ | | 155-199, 276-277, 280-299 |
| 613 | 24 | PK | | 7-6 | 28-22-12 | D01330 | 13 | | | | | | TB0070Y | A021 | BJ | | 278 |
| 614 | 24 | PK | | 14-0 | 28-22-12 | D01330 | 14 | | | | | | D04644J | 6 | | | 050-099, 150-199, 275-277, 280-299 |
| 614 | 24 | PK | | 13-0 | 28-22-12 | D01330 | 14 | | | | | | D04644J | 6 | | | 278 |
| 615 | 22 | PA | | 14-0 | 28-42-12 | D04708J | 14 | | | | | | D01330 | 15 | | | 050-099, 150-199, 275-277, 280-299 |
| 615 | 22 | PA | | 13-1 | 28-42-12 | D04708J | 14 | | | | | | D01330 | 15 | | | 278 |
| 616 | 24 | PK | | 14-0 | 28-42-31 | D04708J | 9 | | | | | | D01330 | 16 | | | 050-099, 150-199, 275-277, 280-299 |
| 616 | 24 | PK | | 13-1 | 28-42-31 | D04708J | 9 | | | | | | D01330 | 16 | | | 278 |
| 618 | 22 | PA | | 8-0 | 28-42-12 | TB0070Y | C020 | BJ | | | | | D01330 | 18 | | | 050-099 |
| 618 | 22 | PA | | 14-0 | 28-42-12 | D05400J | 7 | | | | | | D01330 | 18 | | | 150-154, 275 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 43

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|---------|-------|------|------|--------|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 618 | 22 | | PA | 14-0 | 28-42-12 | TB0070Y | C020 | BJ | | D01330 | | 18 | | | 155-199, 276-277, 280-299 |
| 618 | 22 | | PA | 7-6 | 28-42-12 | TB0070Y | C020 | BJ | | D01330 | | 18 | | | 278 |
| 61A | 24 | | PK | 3-0 | 36-11-11 | D07962J | | 2 | | D05726J | | 23 | | | 050-099, 150-199, 275-277, 280-299 |
| 61A | 24 | | PK | 3-1 | 36-11-11 | D07962J | | 2 | | D05726J | | 23 | | | 278 |
| 61B | 24 | | PK | 3-0 | 36-11-31 | D07962J | | 4 | | D05726J | | 28 | | | 050-099, 150-199, 275-277, 280-299 |
| 61B | 24 | | PK | 3-1 | 36-11-31 | D07962J | | 4 | | D05726J | | 28 | | | 278 |
| 61E | 18 | | PA | 3-0 | 36-11-51 | D07962J | | 5 | DL | D05726J | | 33 | DK | | 050-099, 155, 162-165, 276 |
| 61E | 18 | | PA | 5-0 | 36-11-51 | D07962J | | 5 | DL | D05910J | | 10 | | | 150-154, 275 |
| 61E | 18 | | PA | 3-0 | 36-11-51 | D07962J | | 5 | DL | D05726J | | 18 | DK | | 156-157, 166-199, 277, 280-299 |
| 61E | 18 | | PA | 3-1 | 36-11-51 | D07962J | | 5 | DL | D05726J | | 18 | DK | | 278 |
| 61F | 24 | | PK | 3-0 | 36-11-51 | D07962J | | 6 | | D05726J | | 10 | | | 050-099, 150-199, 275-277, 280-299 |
| 61F | 24 | | PK | 3-1 | 36-11-51 | D07962J | | 6 | | D05726J | | 10 | | | 278 |
| 61G | 22 | | PA | 6-0 | 36-11-51 | TB0098X | C004 | BJ | | D05726J | | 34 | | | 050-099, 150-199, 275-277, 280-299 |
| 61G | 22 | | PA | 4-2 | 36-11-51 | TB0098X | C004 | BJ | | D05726J | | 34 | | | 278 |
| 61H | 24 | | PK | 3-0 | 36-21-11 | D07962J | | 8 | | D05726J | | 9 | | | 050-099, 150-199, 275-277, 280-299 |
| 61H | 24 | | PK | 3-1 | 36-21-11 | D07962J | | 8 | | D05726J | | 9 | | | 278 |
| 61K | 18 | | PA | 4-0 | 38-32-14 | D05064J | | 14 | DK | D07962J | | 9 | DL | | 050-099 |
| 61K | 18 | | PA | 4-0 | 38-32-14 | D07962J | | 9 | DL | D05064J | | 14 | DK | | 150-199, 275-277, 280-299 |
| 61K | 18 | | PA | 3-0 | 38-32-14 | D07962J | | 9 | DL | D05064J | | 14 | DK | | 278 |
| 61L | 16 | | PA | 5-0 | 73-21-20 | D04710J | | 47 | FM | D07968J | | 6 | FL | | 050-099, 150-199, 275-277, 280-299 |
| 61L | 16 | | PA | 3-11 | 73-21-20 | D04710J | | 47 | FM | D07968J | | 6 | FL | | 278 |
| 61N | 18 | | PA | 4-0 | 38-32-11 | D07962J | | 12 | DL | D05064J | | 21 | | | 050-099, 150-199, 275-277, 280-299 |
| 61N | 18 | | PA | 3-0 | 38-32-11 | D07962J | | 12 | DL | D05064J | | 21 | | | 278 |
| 624 | 20 | | PQ | SR | 8-0 | 28-42-31 | GD00102 | D.. | 2 | D01330 | | 24 | | | 050-099, 150-199, 275-277, 280-299 |
| 624 | 20 | | PQ | SR | 6-10 | 28-42-31 | GD00102 | D.. | 2 | D01330 | | 24 | | | 278 |
| 624Z | | | | SR | 0-0 | 28-42-31 | GD00102 | DED | | D01330 | | DED | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 44
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 629 | 24 | | PK | 4-0 | 28-22-12 | D05000P | | 38 | | | | TB0070Y | A021 | BJ | 050-099, 155-199, 276-277, 280-299 | |
| 629 | 24 | | PK | 3-6 | 28-22-12 | D05000P | | 38 | | | | TB0070Y | A021 | BJ | 278 | |
| 62B | 24 | | PK | 5-0 | 73-21-17 | D07968J | | 16 | | | | D04710J | 30 | | 050-099, 150-199, 275-277, 280-299 | |
| 62B | 24 | | PK | 3-11 | 73-21-17 | D07968J | | 16 | | | | D04710J | 30 | | 278 | |
| 62C | 24 | | PK | 12-0 | 74-31-11 | D05000P | | 15 | | | | D05400J | 16 | | 050-099, 150-199, 275-277, 280-299 | |
| 62C | 24 | | PK | 11-2 | 74-31-11 | D05000P | | 15 | | | | D05400J | 16 | | 278 | |
| 62D | 22 | | PA | 5-0 | 74-31-11 | D04732J | | 5 | | | | TB0100Y | A026 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 62D | 22 | | PA | 4-3 | 74-31-11 | D04732J | | 5 | | | | TB0100Y | A026 | BJ | 278 | |
| 62E | 22 | | PA | 5-0 | SPARE | D04732J | | 4 | | | | TB0100Y | CAP | Y | 050-099, 150-199, 275-277, 280-299 | |
| 62E | 22 | | PA | 4-3 | SPARE | D04732J | | 4 | | | | TB0100Y | CAP | Y | 278 | |
| 62F | 22 | | PQ PA | 5-0 | 74-31-11 | D04720J | | 28 | | | | TB0098Y | A012 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 62F | 22 | | PQ PA | 3-9 | 74-31-11 | D04720J | | 28 | | | | TB0098Y | A012 | BJ | 278 | |
| 62FZ | | | PA | 0-0 | 74-31-11 | D04720J | | DED | | | | TB0098Y | DED | | ALL | |
| 62G | 22 | | PQ PB | 5-0 | 74-31-11 | D04720J | | 27 | | | | TB0098Y | A012 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 62G | 22 | | PQ PB | 3-9 | 74-31-11 | D04720J | | 27 | | | | TB0098Y | A012 | BJ | 278 | |
| 62GZ | | | PB | 0-0 | 74-31-11 | D04720J | | DED | | | | TB0098Y | DED | | ALL | |
| 62H | 22 | | PQ PC | 5-0 | 74-31-11 | D04720J | | 29 | | | | TB0098X | C006 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 62H | 22 | | PQ PC | 3-9 | 74-31-11 | D04720J | | 29 | | | | TB0098X | C006 | BJ | 278 | |
| 62HZ | | | PC | 0-0 | 74-31-11 | D04720J | | DED | | | | TB0098X | DED | | ALL | |
| 62J | 24 | | PK | 6-0 | 74-31-11 | D04710J | | 6 | | | | TB0098X | D006 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 62J | 24 | | PK | 4-9 | 74-31-11 | D04710J | | 6 | | | | TB0098X | D006 | BJ | 278 | |
| 62K | 24 | | PK | 5-0 | 75-23-11 | D07968J | | 17 | | | | D04732J | 20 | | 050-099, 150-199, 275-277, 280-299 | |
| 62K | 24 | | PK | 3-5 | 75-23-11 | D07968J | | 17 | | | | D04732J | 20 | | 278 | |
| 62L | 16 | | PA | 5-0 | 73-21-20 | D07968J | | 18 | FL | | | D04710J | 18 | FM | 050-099, 150-199, 275-277, 280-299 | |
| 62L | 16 | | PA | 3-11 | 73-21-20 | D07968J | | 18 | FL | | | D04710J | 18 | FM | 278 | |
| 62M | 20 | | PA | 5-0 | 75-32-11 | D07968J | | 19 | | | | D04714J | 36 | | 150-157 | |
| 62M | 20 | | PA | 5-0 | SPARE | D07968J | | 19 | | | | D04714J | 36 | | 162-199 | |
| 62N | 20 | | PA | 5-0 | 75-32-11 | D07968J | | 20 | | | | D04714J | 37 | | 150-157 | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 45

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 62N | 20 | | PA | | 5-0 | SPARE | D07968J | | 20 | | | | D04714J | | 37 | | 162-199 |
| 62P | 20 | | PA | | 5-0 | 73-21-19 | D07968J | | 21 | | | | D04710J | | 31 | | 050-099, 150-199, 275-277, 280-299 |
| 62P | 20 | | PA | | 3-11 | 73-21-19 | D07968J | | 21 | | | | D04710J | | 31 | | 278 |
| 62T | 24 | | PK | | 5-0 | 77-31-11 | D07968J | | 23 | | | | D04714J | | 25 | | 050-099, 150-199, 275-277, 280-299 |
| 62T | 24 | | PK | | 3-9 | 77-31-11 | D07968J | | 23 | | | | D04714J | | 25 | | 278 |
| 62W | 24 | | PK | | 5-0 | 78-34-11 | D07968J | | 24 | | | | TB0098Y | C012 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 62W | 24 | | PK | | 3-5 | 78-34-11 | D07968J | | 24 | | | | TB0098Y | C012 | BJ | | 278 |
| 62X | 24 | | PK | | 6-0 | 78-34-11 | TB0098Y | | C012 | BJ | | | D04710J | | 29 | | 050-099, 150-199, 275-277, 280-299 |
| 62X | 24 | | PK | | 4-9 | 78-34-11 | TB0098Y | | C012 | BJ | | | D04710J | | 29 | | 278 |
| 62Y | 24 | | PK | | 6-0 | 78-34-11 | TB0098X | | B006 | BJ | | | D04710J | | 50 | | 050-099, 150-199, 275-277, 280-299 |
| 62Y | 24 | | PK | | 4-9 | 78-34-11 | TB0098X | | B006 | BJ | | | D04710J | | 50 | | 278 |
| 630 | 24 | | PK | | 12-0 | 28-22-12 | D04708J | | 11 | | | | TB0070Y | A021 | BJ | | 050-099, 155-199, 276-277, 280-299 |
| 630 | 24 | | PK | | 11-11 | 28-22-12 | D04708J | | 11 | | | | TB0070Y | A021 | BJ | | 278 |
| 633 | 22 | | PQ | RX | 8-0 | 33-16-17 | TB0070Y | | C031 | BJ | | | D00874 | | 3 | | ALL |
| 633Z | | | | RX | 0-0 | 33-16-17 | TB0070Y | | DED | | | | D00874 | | DED | | ALL |
| 634 | 22 | | PA | | 8-0 | 33-16-17 | TB0070Z | | 34 | BJ | | | D00874 | | 4 | | ALL |
| 635 | 16 | | PA | | 8-0 | 33-11-14 | D00874 | | 5 | FM | | | GD00086 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 635 | 16 | | PA | | 7-8 | 33-11-14 | D00874 | | 5 | FM | | | GD00086 | A.. | 2 | | 278 |
| 636 | 22 | | PQ | DE | 13-0 | 28-31-11 | D12172 | | 12 | | | | TB0100Y | C028 | BJ | | 050-099, 155-199, 276-277, 280-299 |
| 636 | 22 | | PQ | DE | 11-10 | 28-31-11 | D12172 | | 12 | | | | TB0100Y | C028 | BJ | | 278 |
| 636Z | | | | DE | 0-0 | 28-31-11 | D12172 | | DED | | | | TB0100Y | DED | | | 050-099, 155-199, 276-299 |
| 637 | 24 | | PK | | 13-0 | SPARE | D00874 | | CAP | Y | | | TB0100Y | C027 | BJ | | 152, 154, 156, 162, 166-199 |
| 638 | 24 | | PK | | 8-0 | SPARE | D00874 | | CAP | Y | | | D05000P | CAP | Y | | 152, 154, 156, 162, 166-199 |
| 639 | 20 | | PA | | 5-0 | 28-31-11 | TB0100Y | | A028 | BJ | | | D04708J | | 13 | | 050-099, 155-199, 276-277, 280-299 |
| 639 | 20 | | PA | | 4-3 | 28-31-11 | TB0100Y | | A028 | BJ | | | D04708J | | 13 | | 278 |
| 63A | 24 | | PK | | 5-0 | 78-36-11 | D07968J | | 25 | | | | D04732J | | 10 | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 46
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 63A | 24 | | PK | 3-5 | 78-36-11 | D07968J | | 25 | | | | | D04732J | 10 | | | 278 |
| 63B | 24 | | PK | 10-0 | 78-36-11 | D07968J | | 26 | | | | | TB0098Y | A028 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 63B | 24 | | PK | 3-5 | 78-36-11 | D07968J | | 26 | | | | | TB0098Y | A028 | BJ | | 278 |
| 63C | 22 | | PA | 5-0 | 79-32-11 | D07968J | | 27 | | | | | D04720J | 14 | | | 050-099, 150-199, 275-277, 280-299 |
| 63C | 22 | | PA | 2-11 | 79-32-11 | D07968J | | 27 | | | | | D04720J | 14 | | | 278 |
| 63F | 22 | | PA | 4-0 | 31-41-11 | D07970J | | 5 | | | | | D04720J | 9 | | | 050-099, 150-199, 275-277, 280-299 |
| 63F | 22 | | PA | 3-1 | 31-41-11 | D07970J | | 5 | | | | | D04720J | 9 | | | 278 |
| 63G | 20 | | PQ AC | 11-0 | 78-34-11 | D04710J | | 51 | | | | | D04718J | 24 | | | 050-099, 150-199, 275-277, 280-299 |
| 63G | 20 | | PQ AC | 1-9 | 78-34-11 | D04710J | | 51 | | | | | D04718J | 24 | | | 278 |
| 63GZ | | | AC | 0-0 | 78-34-11 | D04710J | | | | | GA | | D04718J | | | GE | ALL |
| 63H | 24 | | PK | 2-0 | 31-41-13 | TB0100Z | | 21 | BJ | | | | TB0100Z | 22 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 63H | 24 | | PK | 0-7 | 31-41-13 | TB0100Z | | 21 | BJ | | | | TB0100Z | 22 | BJ | | 278 |
| 63J | 24 | | PK | 6-0 | 31-51-31 | D04726J | | 1 | | | | | TB0100Z | 20 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 63J | 24 | | PK | 4-5 | 31-51-31 | D04726J | | 1 | | | | | TB0100Z | 20 | BJ | | 278 |
| 63M | 24 | | PK | 5-0 | 33-16-14 | D04644J | | 1 | | | | | TB0098Y | C033 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 63M | 24 | | PK | 4-3 | 33-16-14 | D04644J | | 1 | | | | | TB0098Y | C033 | BJ | | 278 |
| 63P | 24 | | PK | 5-0 | 21-58-13 | D07960J | | 15 | | | | | D04644J | 10 | | | 050-099, 150-199, 275-277, 280-299 |
| 63P | 24 | | PK | 3-5 | 21-58-13 | D07960J | | 15 | | | | | D04644J | 10 | | | 278 |
| 63V | 20 | | PQ CH | 8-0 | 78-34-21 | D04710J | | 43 | | | | | TB0104X | D027 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 63V | 20 | | PQ CH | 5-1 | 78-34-21 | D04710J | | 43 | | | | | TB0104X | D027 | BJ | | 278 |
| 63VZ | | | CH | 0-0 | 78-34-21 | TB0104X | | DED | | | | | D04710J | | | GF | ALL |
| 63W | 20 | | PA | 5-0 | 78-34-11 | D04710J | | 2 | | | | | TB0098Y | A028 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 63W | 20 | | PA | 4-9 | 78-34-11 | D04710J | | 2 | | | | | TB0098Y | A028 | BJ | | 278 |
| 642 | 22 | | PA | 14-0 | SPARE | D00874 | | CAP | Y | | | | D05180J | 21 | | | 152, 154, 156, 162, 166-199 |
| 643 | 20 | | PA | 13-0 | 33-11-14 | D00874 | | 13 | | | | | TB0102Y | A013 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 643 | 20 | | PA | 13-1 | 33-11-14 | D00874 | | 13 | | | | | TB0102Y | A013 | BJ | | 278 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 47

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 644 | 24 | | PK | 7-0 | 34-61-14 | D12174 | | 7 | | | | | TB0070X | B009 | BJ | | 050-099, 155-199, 276-277, 280-299 |
| 644 | 24 | | PK | 8-0 | 34-61-14 | D12174 | | 7 | | | | | TB0070X | B009 | BJ | | 150-154 |
| 644 | 24 | | PK | 6-10 | 34-61-14 | D12174 | | 7 | | | | | TB0070X | B009 | BJ | | 278 |
| 645 | 16 | | PA | 13-0 | 33-11-14 | D00874 | | 15 | FM | | | | TB0096F | A015 | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 645 | 16 | | PA | 13-6 | 33-11-14 | D00874 | | 15 | FM | | | | TB0096F | A015 | 2 | | 278 |
| 648 | 20 | | PA | 8-0 | 33-16-11 | D00874 | | 18 | | | | | GD00086 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 648 | 20 | | PA | 7-8 | 33-16-11 | D00874 | | 18 | | | | | GD00086 | D.. | 2 | | 278 |
| 649 | 24 | | PK | 13-0 | 33-16-11 | D00874 | | 19 | | | | | TB0100Y | C013 | BJ | | ALL |
| 64A | 24 | | PK | 6-0 | 24-22-11 | D10110 | | 21 | | | | | D04778J | 2 | | | 050-099, 150-199, 275-277, 280-299 |
| 64A | 24 | | PK | 5-1 | 24-22-11 | D10110 | | 21 | | | | | D04778J | 2 | | | 278 |
| 64B | 24 | | PK | 6-0 | 24-22-11 | D10110 | | 23 | | | | | D04778J | 42 | | | 050-099, 150-199, 275-277, 280-299 |
| 64B | 24 | | PK | 5-1 | 24-22-11 | D10110 | | 23 | | | | | D04778J | 42 | | | 278 |
| 64C | 24 | | PK | 8-0 | 24-22-41 | D10112 | | 23 | | | | | TB0096X | A002 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 64C | 24 | | PK | 7-1 | 24-22-41 | D10112 | | 23 | | | | | TB0096X | A002 | BJ | | 278 |
| 64D | 24 | | PK | 8-0 | 24-22-41 | D10112 | | 21 | | | | | TB0096D | C005 | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 64D | 24 | | PK | 7-1 | 24-22-41 | D10112 | | 21 | | | | | TB0096D | C005 | 2 | | 278 |
| 64F | 24 | | PV | 4-0 | 80-11-11 | TB0106X | | A005 | BJ | | | | D05400J | 5 | | | ALL |
| 64FZ | | | SK | 0-0 | 80-11-11 | TB0106X | | DED | | | | | D05400J | DED | | | ALL |
| 64G | 24 | | PV | 4-0 | 80-11-11 | TB0106X | | A006 | BJ | | | | D05400J | 6 | | | ALL |
| 64GZ | | | SL | 0-0 | 80-11-11 | TB0106X | | DED | | | | | D05400J | DED | | | ALL |
| 64H | 24 | | PK | 8-0 | 24-51-71 | D06154P | | 21 | | | | | D04778J | 43 | | | 050-099, 150-199, 275-277, 280-299 |
| 64H | 24 | | PK | 7-9 | 24-51-71 | D06154P | | 21 | | | | | D04778J | 43 | | | 278 |
| 64J | 24 | | PK | 7-0 | 24-51-42 | D05400J | | 17 | | | | | D05848P | 9 | | | 050-099, 150-199, 275-277, 280-299 |
| 64J | 24 | | PK | 6-11 | 24-51-42 | D05400J | | 17 | | | | | D05848P | 9 | | | 278 |
| 64L | 22 | | PA | 5-0 | 33-51-11 | TB0106X | | B004 | BJ | | | | D04710J | 16 | | | ALL |
| 64M | 22 | | PA | 5-0 | 33-51-11 | TB0106X | | B005 | BJ | | | | D05180J | 19 | | | 050-099, 150-199, 275-277, 280-299 |
| 64M | 22 | | PA | 5-2 | 33-51-11 | TB0106X | | B005 | BJ | | | | D05180J | 19 | | | 278 |
| 64N | 22 | | PA | 8-0 | 33-16-17 | D07968J | | 4 | | | | | D06152P | 19 | | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 48

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | | |
| 64N | 22 | | PA | 7-8 | 33-16-17 | D07968J | | 4 | | | | | | D06152P | 19 | | | 278 |
| 64S | 24 | | PK | 5-0 | 35-21-11 | D05180J | | 6 | | | | | | TB0106X | A007 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 64S | 24 | | PK | 5-2 | 35-21-11 | D05180J | | 6 | | | | | | TB0106X | A007 | BJ | | 278 |
| 64V | 24 | | PK | 5-0 | 32-61-14 | D04990J | | 28 | | | | | | D04726J | 2 | | | 050-099, 150-199, 275-277, 280-299 |
| 64V | 24 | | PK | 1-9 | 32-61-14 | D04990J | | 28 | | | | | | D04726J | 2 | | | 278 |
| 64W | 24 | | PK | 5-0 | 32-61-14 | D04990J | | 29 | | | | | | D04726J | 3 | | | 050-099, 150-199, 275-277, 280-299 |
| 64W | 24 | | PK | 1-9 | 32-61-14 | D04990J | | 29 | | | | | | D04726J | 3 | | | 278 |
| 64X | 24 | | PK | 5-0 | 32-61-14 | D04990J | | 30 | | | | | | D04644J | 7 | | | 050-099, 150-199, 275-277, 280-299 |
| 64X | 24 | | PK | 1-10 | 32-61-14 | D04990J | | 30 | | | | | | D04644J | 7 | | | 278 |
| 650 | 24 | | PK | 9-0 | 33-16-11 | TB0100Y | | C013 | BJ | | | | | D06152P | 7 | | | 050-099, 150-199, 275-277, 280-299 |
| 650 | 24 | | PK | 8-6 | 33-16-11 | TB0100Y | | C013 | BJ | | | | | D06152P | 7 | | | 278 |
| 651 | 18 | | PA | 5-0 | 33-13-16 | D00548 | | 2 | DK | | | | | D01382 | 1 | DK | | 050-099, 150-199, 275-277, 280-299 |
| 651 | 18 | | PA | 3-1 | 33-13-16 | D00548 | | 2 | DK | | | | | D01382 | 1 | DK | | 278 |
| 652 | 18 | | PA | 7-0 | 33-13-16 | GD00100 | | A.. | 2 | | | | | D01382 | 2 | DK | | 050-099, 150-199, 275-277, 280-299 |
| 652 | 18 | | PA | 6-8 | 33-13-16 | GD00100 | | A.. | 2 | | | | | D01382 | 2 | DK | | 278 |
| 653 | 22 | | PQ | 9-0 | 33-16-17 | D01382 | | 3 | | | | | | TB0068Y | C017 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 653 | 22 | | PQ | 7-6 | 33-16-17 | D01382 | | 3 | | | | | | TB0068Y | C017 | BJ | | 278 |
| 653Z | | | SM | 0-0 | 33-16-17 | D01382 | | DED | | | | | | TB0068Y | DED | | | ALL |
| 654 | 22 | | PQ | 9-0 | 33-16-17 | D01382 | | 4 | | | | | | TB0068Z | 15 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 654 | 22 | | PQ | 7-6 | 33-16-17 | D01382 | | 4 | | | | | | TB0068Z | 15 | BJ | | 278 |
| 654Z | | | SN | 0-0 | 33-16-17 | D01382 | | DED | | | | | | TB0068Z | DED | | | ALL |
| 655 | 24 | | PK | 15-0 | 24-51-13 | D01382 | | 5 | | | | | | D04778J | 26 | | | 050-099, 150-199, 275-277, 280-299 |
| 655 | 24 | | PK | 13-6 | 24-51-13 | D01382 | | 5 | | | | | | D04778J | 26 | | | 278 |
| 656 | 24 | | PK | 15-0 | 24-51-71 | D01382 | | 6 | | | | | | D04778J | 47 | | | 050-099, 150-199, 275-277, 280-299 |
| 656 | 24 | | PK | 13-6 | 24-51-71 | D01382 | | 6 | | | | | | D04778J | 47 | | | 278 |
| 657 | 16 | | PA | 13-0 | 25-31-21 | D01382 | | 7 | FM | | | | | TB0100G | 42 | 2 | | 050-099 |
| 657 | 20 | | PA | 14-0 | 25-31-21 | D01382 | | 7 | | | | | | TB0100G | 42 | 2 | | 150-199 |
| 657 | 16 | | PA | 14-0 | 25-31-21 | D01382 | | 7 | FM | | | | | TB0100G | 42 | 2 | | 275-277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 49

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 657 | 16 | | PA | 12-7 | 25-31-21 | D01382 | 7 | FM | | TB0100G | 42 | 2 | | 278 | | |
| 658 | 24 | | PK | 15-0 | 24-51-13 | D01382 | 8 | | | D04778J | 25 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 658 | 24 | | PK | 13-6 | 24-51-13 | D01382 | 8 | | | D04778J | 25 | | | 278 | | |
| 659 | 22 | | PA | 14-0 | 25-31-21 | D01382 | 9 | | | D04776J | 4 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 659 | 22 | | PA | 13-8 | 25-31-21 | D01382 | 9 | | | D04776J | 4 | | | 278 | | |
| 65D | 20 | | PA | 6-0 | 25-31-21 | TB0100G | 42 | 2 | | D04718J | 22 | | | 050-099, 150-199 | | |
| 65D | 18 | | PA | 6-0 | 25-31-21 | TB0100G | 42 | 2 | | D04718J | 18 | DK | | 275-277, 280-299 | | |
| 65D | 18 | | PA | 4-7 | 25-31-21 | TB0100G | 42 | 2 | | D04718J | 18 | DK | | 278 | | |
| 65E | 16 | | PA | 6-0 | 25-31-21 | TB0100G | 42 | 2 | | D04778J | 13 | FM | | 050-099 | | |
| 65E | 16 | | PA | 7-0 | 25-31-21 | TB0100G | 42 | 2 | | D04778J | 13 | FM | | 150-199 | | |
| 65E | 16 | | PA | 7-0 | 25-31-21 | TB0100G | 42 | 2 | | D04776J | 1 | FM | | 275-276, 280-299 | | |
| 65E | 16 | | PA | 7-0 | 25-31-21 | TB0100G | 42 | 2 | | D04776J | 1 | | | 277 | | |
| 65E | 16 | | PA | 4-11 | 25-31-21 | TB0100G | 42 | 2 | | D04776J | 1 | | | 278 | | |
| 65H | 16 | | PA | 7-0 | 30-42-11 | D05000P | 23 | | | D04966P | 4 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 65H | 16 | | PA | 6-3 | 30-42-11 | D05000P | 23 | | | D04966P | 4 | | | 278 | | |
| 65N | 24 | | PK | 4-0 | 30-34-31 | D07962J | 30 | | | D04708J | 12 | | | 150-199 | | |
| 660 | 24 | | PK | 12-0 | 24-51-13 | D01382 | 10 | | | D07962J | 19 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 660 | 24 | | PK | 11-10 | 24-51-13 | D01382 | 10 | | | D07962J | 19 | | | 278 | | |
| 661 | 22 | | PA | 9-0 | 33-16-17 | D01382 | 11 | | | TB0070Z | 30 | BJ | | 050-099, 150-199, 275-277, 280-299 | | |
| 661 | 22 | | PA | 7-6 | 33-16-17 | D01382 | 11 | | | TB0070Z | 30 | BJ | | 278 | | |
| 662 | 20 | | PA | 9-0 | 24-51-71 | D01382 | 12 | | | GD00102 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 | | |
| 662 | 20 | | PA | 6-10 | 24-51-71 | D01382 | 12 | | | GD00102 | D.. | 2 | | 278 | | |
| 663 | 24 | | PK | 15-0 | 24-11-11 | D01382 | 13 | | | D04778J | 10 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 663 | 24 | | PK | 13-6 | 24-11-11 | D01382 | 13 | | | D04778J | 10 | | | 278 | | |
| 664 | 24 | | PK | 12-0 | 24-32-11 | D01382 | 14 | | | TB0106X | A001 | BJ | | 050-099, 150-199, 275-277, 280-299 | | |
| 664 | 24 | | PK | 12-10 | 24-32-11 | D01382 | 14 | | | TB0106X | A001 | BJ | | 278 | | |
| 668 | 24 | | PK | 13-0 | 24-22-11 | D01382 | 18 | | | TB0098X | A004 | BJ | | 050-099, 150-199, 275-277, 280-299 | | |
| 668 | 24 | | PK | 12-7 | 24-22-11 | D01382 | 18 | | | TB0098X | A004 | BJ | | 278 | | |
| 669 | 20 | | PA | 15-0 | 24-22-11 | D01382 | 19 | | | D04778J | 18 | | | 050-099, 150-199, 275-277, 280-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 50

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 669 | 20 | | PA | 13-6 | 24-22-11 | D01382 | | 19 | | | | | D04778J | 18 | | | 278 |
| 66D | 24 | | PK | 5-0 | 21-24-11 | D07960J | | 27 | | | | | D04708J | 8 | | | 050-099, 150-199 |
| 66E | 24 | | PK | 5-0 | 21-24-11 | D05180J | | 12 | | | | | D04708J | 6 | | | 050-099, 150-199 |
| 66F | 22 | | PA | 5-0 | 21-24-11 | D04708J | | 27 | | | | | TB0100Y | A037 | BJ | | 050-099 |
| 66F | 22 | | PA | 6-0 | 21-24-11 | TB0100Y | | A037 | BJ | | | | D04708J | 27 | | | 150-199 |
| 66G | 24 | | PK | 5-0 | 21-24-11 | D04708J | | 7 | | | | | TB0100Y | A037 | BJ | | 050-099 |
| 66G | 24 | | PK | 6-0 | 21-24-11 | TB0100Y | | A037 | BJ | | | | D04708J | 7 | | | 150-199 |
| 66H | 20 | | PA | 5-0 | 33-42-21 | D07970J | | 12 | | | | | D04644J | 56 | | | 050-099 |
| 66H | 18 | | PA | 5-0 | 33-42-21 | D07970J | | 12 | DL | | | | D04644J | 56 | DK | | 150-199, 275-277, 280-299 |
| 66H | 18 | | PA | 3-7 | 33-42-21 | D07970J | | 12 | DL | | | | D04644J | 56 | DK | | 278 |
| 66J | 20 | | PA | 5-0 | 33-42-21 | D07970J | | 13 | | | | | D04644J | 57 | | | 050-099 |
| 66J | 18 | | PA | 5-0 | 33-42-21 | D07970J | | 13 | DL | | | | D04644J | 57 | DK | | 150-199, 275-277, 280-299 |
| 66J | 18 | | PA | 3-7 | 33-42-21 | D07970J | | 13 | DL | | | | D04644J | 57 | DK | | 278 |
| 66K | 22 | | PA | 8-0 | 25-11-11 | D05934P | | 21 | | | | | D05064J | 11 | | | 050-099, 150-199, 275-277, 280-299 |
| 66K | 22 | | PA | 7-6 | 25-11-11 | D05934P | | 21 | | | | | D05064J | 11 | | | 278 |
| 66L | 22 | | PA | 8-0 | 25-11-11 | D05934P | | 22 | | | | | D05064J | 12 | | | 050-099, 150-199, 275-277, 280-299 |
| 66L | 22 | | PA | 7-6 | 25-11-11 | D05934P | | 22 | | | | | D05064J | 12 | | | 278 |
| 66M | 22 | | PA | 8-0 | 25-11-11 | D05934P | | 23 | | | | | D05064J | 13 | | | 050-099, 150-199, 275-277, 280-299 |
| 66M | 22 | | PA | 7-6 | 25-11-11 | D05934P | | 23 | | | | | D05064J | 13 | | | 278 |
| 66N | 24 | | PK | 5-0 | 73-33-11 | D07968J | | 29 | | | | | D04732J | 3 | | | 050-099 |
| 66N | 24 | | PK | 4-0 | 73-33-11 | D04732J | | 3 | | | | | D07968J | 29 | | | 150-199, 275-277, 280-299 |
| 66N | 24 | | PK | 3-5 | 73-33-11 | D04732J | | 3 | | | | | D07968J | 29 | | | 278 |
| 66P | 24 | | PK | 4-0 | 33-11-13 | D07970J | | 16 | | | | | TB0098X | A008 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 66P | 24 | | PK | 3-7 | 33-11-13 | D07970J | | 16 | | | | | TB0098X | A008 | BJ | | 278 |
| 66R | 24 | | PK | 4-0 | 33-11-13 | D07968J | | 13 | | | | | TB0098X | B008 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 66R | 24 | | PK | 3-5 | 33-11-13 | D07968J | | 13 | | | | | TB0098X | B008 | BJ | | 278 |
| 66S | 24 | | PK | 7-0 | 33-13-16 | D05000P | | 29 | | | | | TB0064Y | C019 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 66S | 24 | | PK | 6-4 | 33-13-16 | D05000P | | 29 | | | | | TB0064Y | C019 | BJ | | 278 |
| 66T | 16 | | PA | 6-0 | 27-32-31 | D05000P | | 6 | FL | | | | D04968P | 27 | FM | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 51

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 66T | 16 | | PA | 6-2 | 27-32-31 | D05000P | 6 | FL | | D04968P | 27 | FM | | 278 | | |
| 66U | 16 | | PA | 7-0 | 28-22-11 | D05918P | 1 | | | D05910J | 4 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 66U | 16 | | PA | 6-5 | 28-22-11 | D05918P | 1 | | | D05910J | 4 | | | 278 | | |
| 66V | 16 | | PA | 7-0 | 28-22-11 | D05918P | 2 | | | D05910J | 5 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 66V | 16 | | PA | 6-5 | 28-22-11 | D05918P | 2 | | | D05910J | 5 | | | 278 | | |
| 66W | 16 | | PA | 7-0 | 28-22-11 | D05918P | 3 | | | D05910J | 6 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 66W | 16 | | PA | 6-5 | 28-22-11 | D05918P | 3 | | | D05910J | 6 | | | 278 | | |
| 66X | 16 | | PA | 7-0 | 28-22-11 | D05918P | 4 | | | D05910J | 7 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 66X | 16 | | PA | 6-5 | 28-22-11 | D05918P | 4 | | | D05910J | 7 | | | 278 | | |
| 66Y | 16 | | PA | 7-0 | 28-22-11 | D05918P | 5 | | | D05910J | 8 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 66Y | 16 | | PA | 6-5 | 28-22-11 | D05918P | 5 | | | D05910J | 8 | | | 278 | | |
| 66Z | 16 | | PA | 7-0 | 28-22-11 | D05918P | 6 | | | D05910J | 9 | | | 050-099, 150-156, 162-166, 275-276 | | |
| 670 | 24 | | PK | 16-0 | 24-22-11 | D01382 | 20 | | | D10110 | 22 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 670 | 24 | | PK | 15-0 | 24-22-11 | D01382 | 20 | | | D10110 | 22 | | | 278 | | |
| 671 | 24 | | PK | 15-0 | 24-22-11 | D01382 | 21 | | | D04778J | 11 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 671 | 24 | | PK | 13-6 | 24-22-11 | D01382 | 21 | | | D04778J | 11 | | | 278 | | |
| 672 | 20 | | PA | 15-0 | 24-22-11 | D01382 | 22 | | | D04778J | 19 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 672 | 20 | | PA | 13-6 | 24-22-11 | D01382 | 22 | | | D04778J | 19 | | | 278 | | |
| 673 | 24 | | PK | 14-0 | 24-51-13 | D01382 | 23 | | | D05402J | 4 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 673 | 24 | | PK | 12-7 | 24-51-13 | D01382 | 23 | | | D05402J | 4 | | | 278 | | |
| 674 | 24 | | PK | 13-0 | 24-51-71 | D01382 | 24 | | | TB0100X | A004 | BJ | | 050-099, 150-199, 275-277, 280-299 | | |
| 674 | 24 | | PK | 12-7 | 24-51-71 | D01382 | 24 | | | TB0100X | A004 | BJ | | 278 | | |
| 675 | 24 | | PK | 15-0 | 24-27-11 | D01382 | 25 | | | D04778J | 22 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 675 | 24 | | PK | 13-6 | 24-27-11 | D01382 | 25 | | | D04778J | 22 | | | 278 | | |
| 676 | 24 | | PK | 15-0 | 24-27-11 | D01382 | 26 | | | D04778J | 21 | | | 050-099, 150-199, 275-277, 280-299 | | |
| 676 | 24 | | PK | 13-6 | 24-27-11 | D01382 | 26 | | | D04778J | 21 | | | 278 | | |

WIRE LIST

D280T132

91-21-11
Section W0060
Page 52
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 677 | 22 | | PA | 9-0 | 33-16-17 | D01382 | | 27 | | | | | TB0070Z | 29 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 677 | 22 | | PA | 7-6 | 33-16-17 | D01382 | | 27 | | | | | TB0070Z | 29 | BJ | | 278 |
| 678 | 24 | | PK | 14-0 | 24-22-12 | D01382 | | 28 | | | | | D04778J | 7 | | | 050-099, 150-199, 275-277, 280-299 |
| 678 | 24 | | PK | 13-6 | 24-22-12 | D01382 | | 28 | | | | | D04778J | 7 | | | 278 |
| 679 | 24 | | PK | 15-0 | 24-27-11 | D01382 | | 29 | | | | | D04778J | 23 | | | 050-099, 150-199, 275-277, 280-299 |
| 679 | 24 | | PK | 13-6 | 24-27-11 | D01382 | | 29 | | | | | D04778J | 23 | | | 278 |
| 67A | 12 | | PA | 8-0 | 28-22-12 | D05934P | | 2 | | | | | D04718J | 23 | | | ALL |
| 67B | 12 | | PA | 8-0 | 28-22-12 | D05934P | | 4 | | | | | D04718J | 27 | | | ALL |
| 67C | 12 | | PA | 8-0 | 28-22-12 | D05934P | | 6 | | | | | D04718J | 15 | | | ALL |
| 67D | 24 | | PK | 5-0 | 32-42-11 | TB0102D | | | C018 | 2 | | | D04726J | 20 | | | 050-099, 150-199, 275-277, 280-299 |
| 67D | 24 | | PK | 4-6 | 32-42-11 | TB0102D | | | C018 | 2 | | | D04726J | 20 | | | 278 |
| 67F | 16 | | PA | 7-0 | 28-22-11 | D05918P | | 6 | | | | | D05910J | 9 | | | 157, 167-199, 277, 280-299 |
| 67F | 16 | | PA | 6-5 | 28-22-11 | D05918P | | 6 | | | | | D05910J | 9 | | | 278 |
| 67G | 22 | | PA | 4-0 | 28-41-13 | TB0100Y | | | A012 | | BJ | | D05400J | 4 | | | 157, 167-199, 277, 280-299 |
| 67G | 22 | | PA | 3-9 | 28-41-13 | TB0100Y | | | A012 | | BJ | | D05400J | 4 | | | 278 |
| 67P | 16 | | PA | 6-0 | 25-31-31 | D04778J | | | 1 | | FM | | TB0100G | 41 | 2 | | 277, 280-299 |
| 67P | 16 | | PA | 4-9 | 25-31-31 | D04778J | | | 1 | | FM | | TB0100G | 41 | 2 | | 278 |
| 67R | 16 | | PA | 6-0 | 25-31-31 | D04718J | | | 11 | | FM | | TB0100G | 41 | 2 | | 277, 280-299 |
| 67R | 16 | | PA | 4-7 | 25-31-31 | D04718J | | | 11 | | FM | | TB0100G | 41 | 2 | | 278 |
| 67W | 22 | | PQ | AK | 14-0 | 73-21-11 | D02083 | | 16 | | | | D04710J | 22 | | | 050-099, 150-199, 275-277, 280-299 |
| 67W | 22 | | PQ | AK | 13-6 | 73-21-11 | D02083 | | 16 | | | | D04710J | 22 | | | 278 |
| 67WZ | | | | AK | 0-0 | 73-21-11 | D02083 | | | | | FD | D04710J | | | FC | ALL |
| 67Y | 22 | | PQ | AH | 14-0 | 73-21-11 | D02083 | | 22 | | | | D04710J | 20 | | | 050-099, 150-199, 275-277, 280-299 |
| 67Y | 22 | | PQ | AH | 13-6 | 73-21-11 | D02083 | | 22 | | | | D04710J | 20 | | | 278 |
| 67YZ | | | | AH | 0-0 | 73-21-11 | D02083 | | | | | FD | D04710J | | | FC | ALL |
| 680 | 24 | | PK | | 15-0 | 24-22-12 | D01382 | | 30 | | | | D04778J | 20 | | | 050-099, 150-199, 275-277, 280-299 |
| 680 | 24 | | PK | | 13-6 | 24-22-12 | D01382 | | 30 | | | | D04778J | 20 | | | 278 |
| 681 | 24 | | PK | | 15-0 | 24-22-12 | D01382 | | 31 | | | | D04778J | 14 | | | 050-099, 150-199, 275-277, 280-299 |
| 681 | 24 | | PK | | 13-6 | 24-22-12 | D01382 | | 31 | | | | D04778J | 14 | | | 278 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 53

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 682 | 24 | | PK | 12-0 | 24-32-11 | D01382 | | 32 | | | TB0106X | B001 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 682 | 24 | | PK | 12-10 | 24-32-11 | D01382 | | 32 | | | TB0106X | B001 | BJ | | 278 |
| 684 | 20 | | PA | 8-0 | 25-31-21 | D01382 | | 34 | | | D05000P | 30 | | | 050-099, 150-199 |
| 684 | 16 | | PA | 8-0 | 25-31-21 | D01382 | | 34 | FM | | D05000P | 30 | FL | | 275-277, 280-299 |
| 684 | 16 | | PA | 7-3 | 25-31-21 | D01382 | | 34 | FM | | D05000P | 30 | FL | | 278 |
| 685 | 24 | | PK | 15-0 | 24-51-71 | D01382 | | 35 | | | D04778J | 45 | | | 050-099, 150-199, 275-277, 280-299 |
| 685 | 24 | | PK | 13-6 | 24-51-71 | D01382 | | 35 | | | D04778J | 45 | | | 278 |
| 687 | 22 | | PA | 12-0 | 25-31-11 | D01382 | | 37 | | | TB0102X | A003 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 687 | 22 | | PA | 12-7 | 25-31-11 | D01382 | | 37 | | | TB0102X | A003 | BJ | | 278 |
| 688 | 22 | | PQ | 5-0 | 28-31-11 | D05402J | DC | 1 | | | TB0100Y | C028 | BJ | | 050-099, 155-199, 276-277, 280-299 |
| 688 | 22 | | PQ | 3-10 | 28-31-11 | D05402J | DC | 1 | | | TB0100Y | C028 | BJ | | 278 |
| 688Z | | | | 0-0 | 28-31-11 | D05402J | DC | DED | | | TB0100Y | DED | | | 050-099, 155-199, 276-299 |
| 689 | 24 | | PK | 19-0 | 24-51-42 | D01382 | | 39 | | | D05848P | 11 | | | 050-099, 150-199, 275-277, 280-299 |
| 689 | 24 | | PK | 17-4 | 24-51-42 | D01382 | | 39 | | | D05848P | 11 | | | 278 |
| 68F | 24 | | PK | 6-0 | 21-45-22 | D07960J | | 17 | | | D04708J | 35 | | | 050-099, 275 |
| 68F | 24 | | PK | 5-0 | 21-45-22 | D07960J | | 17 | | | D04708J | 35 | | | 150-199, 276-277, 280-299 |
| 68F | 24 | | PK | 3-6 | 21-45-22 | D07960J | | 17 | | | D04708J | 35 | | | 278 |
| 690 | 24 | | PK | 19-0 | 24-51-42 | D01382 | | 40 | | | D05848P | 10 | | | 050-099, 150-199, 275-277, 280-299 |
| 690 | 24 | | PK | 17-4 | 24-51-42 | D01382 | | 40 | | | D05848P | 10 | | | 278 |
| 695 | 22 | | PQ | 5-0 | 28-31-11 | D04708J | DD | 32 | | | TB0100Y | C028 | BJ | | 050-099, 155-199, 276-277, 280-299 |
| 695 | 22 | | PQ | 4-3 | 28-31-11 | D04708J | DD | 32 | | | TB0100Y | C028 | BJ | | 278 |
| 695Z | | | | 0-0 | 28-31-11 | D04708J | DD | DED | | | TB0100Y | DED | | | 050-099, 155-199, 276-299 |
| 696 | 20 | | PA | 7-0 | 34-61-14 | D12174 | | 8 | | | GD00263 | D.. | 2 | | 050-099, 150-154 |
| 696 | 20 | | PA | 6-0 | 34-61-14 | D12174 | | 8 | | | GD00263 | D.. | 2 | | 155-199, 276-277, 280-299 |
| 696 | 20 | | PA | 5-4 | 34-61-14 | D12174 | | 8 | | | GD00263 | D.. | 2 | | 278 |
| 698 | 16 | | PA | 7-0 | 25-31-31 | D01382 | | 48 | FM | | D05000P | 5 | FL | | 277 |
| 698 | 16 | | PA | 7-3 | 25-31-31 | D01382 | | 48 | FM | | D05000P | 5 | FL | | 278 |
| 698 | 16 | | PA | 8-0 | 25-31-31 | D01382 | | 48 | FM | | D05000P | 5 | FL | | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 54
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | | |
| 699 | 16 | | PA | | 13-0 | 25-31-31 | D01382 | | 49 | FM | | | | TB0100G | 41 | 2 | | 277, 280-299 |
| 699 | 16 | | PA | | 12-7 | 25-31-31 | D01382 | | 49 | FM | | | | TB0100G | 41 | 2 | | 278 |
| 69A | 22 | | PQ | AJ | 14-0 | 73-21-11 | D02083 | | 21 | | | | | D04710J | 17 | | | 050-099, 150-199, 275-277, 280-299 |
| 69A | 22 | | PQ | AJ | 13-6 | 73-21-11 | D02083 | | 21 | | | | | D04710J | 17 | | | 278 |
| 69AZ | | | | AJ | 0-0 | 73-21-11 | D02083 | | | | FD | | | D04710J | | | FC | ALL |
| 69D | 22 | | PQ | JD | 8-0 | 73-21-11 | TB0070X | | A002 | BJ | | | | D02083 | 15 | | | 050-099, 150-199, 275-277, 280-299 |
| 69D | 22 | | PQ | JD | 7-5 | 73-21-11 | TB0070X | | A002 | BJ | | | | D02083 | 15 | | | 278 |
| 69DZ | | | | JD | 0-0 | 73-21-11 | TB0070X | | B002 | BJ | | | | D02083 | DED | | | 050-099, 162-199, 277-299 |
| 69DZ | | | | JD | 0-0 | 73-21-11 | TB0070X | | DED | | | | | D02083 | DED | | | 150-157, 275-276 |
| 700 | 20 | | PA | | 12-0 | 28-31-11 | D05000P | | 13 | | | | | TB0100Y | A028 | BJ | | 050-099, 155-199, 276-277, 280-299 |
| 700 | 20 | | PA | | 11-2 | 28-31-11 | D05000P | | 13 | | | | | TB0100Y | A028 | BJ | | 278 |
| 701 | 18 | | PA | | 7-0 | 33-13-16 | D00876 | | 1 | DK | | | | TB0064G | 7 | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 701 | 18 | | PA | | 7-1 | 33-13-16 | D00876 | | 1 | DK | | | | TB0064G | 7 | 2 | | 278 |
| 702 | 18 | | PA | | 7-0 | 33-13-16 | D00876 | | 2 | DK | | | | GD00100 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 702 | 18 | | PA | | 6-0 | 33-13-16 | D00876 | | 2 | DK | | | | GD00100 | A.. | 2 | | 278 |
| 703 | 22 | | PQ | SB | 7-0 | 33-16-17 | TB0070Y | | A031 | BJ | | | | D00876 | 3 | | | 050-099, 150-199, 275-277, 280-299 |
| 703 | 22 | | PQ | SB | 6-10 | 33-16-17 | TB0070Y | | A031 | BJ | | | | D00876 | 3 | | | 278 |
| 703Z | | | | SB | 0-0 | 33-16-17 | TB0070Y | | DED | | | | | D00876 | DED | | | ALL |
| 704 | 22 | | PA | | 7-0 | 33-16-17 | TB0070Z | | 34 | BJ | | | | D00876 | 4 | | | 050-099, 150-199, 275-277, 280-299 |
| 704 | 22 | | PA | | 6-10 | 33-16-17 | TB0070Z | | 34 | BJ | | | | D00876 | 4 | | | 278 |
| 705 | 20 | | PA | | 7-0 | 30-41-11 | D00876 | | 5 | | | | | GD00084 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 705 | 20 | | PA | | 6-4 | 30-41-11 | D00876 | | 5 | | | | | GD00084 | A.. | 2 | | 278 |
| 706 | 20 | | PA | | 7-0 | 30-41-11 | D00876 | | 6 | | | | | GD00084 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 706 | 20 | | PA | | 6-4 | 30-41-11 | D00876 | | 6 | | | | | GD00084 | A.. | 2 | | 278 |
| 707 | 20 | | PA | | 12-0 | 28-31-11 | D12174 | | 2 | | | | | TB0100Y | A028 | BJ | | 050-099, 155-199, 276-277, 280-299 |
| 707 | 20 | | PA | | 11-11 | 28-31-11 | D12174 | | 2 | | | | | TB0100Y | A028 | BJ | | 278 |
| 708 | 22 | | PQ | DK | 12-0 | 28-31-12 | D12172 | | 9 | | | | | TB0096D | A033 | 2 | | 050, 155-199, 277, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 55

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 708 | 22 | PQ | DK | | 20-0 | 28-31-12 | TB0096D | A033 | 2 | | D12172 | 9 | | | 051-099 |
| 708 | 22 | PQ | DK | | 12-4 | 28-31-12 | D12172 | | 9 | | TB0096D | A033 | 2 | | 278 |
| 708Z | | | DK | | 0-0 | 28-31-12 | D12172 | DED | | | TB0096D | DED | | | 050, 155-199, 277-299 |
| 708Z | | | DK | | 0-0 | 28-31-12 | TB0096D | DED | | | D12172 | DED | | | 051-099 |
| 709 | 22 | PA | | | 13-0 | 30-41-11 | D00876 | | 9 | | D05064J | 8 | | | 050-099, 150-199, 275-277, 280-299 |
| 709 | 22 | PA | | | 12-2 | 30-41-11 | D00876 | | 9 | | D05064J | 8 | | | 278 |
| 70B | 20 | PA | | | 7-0 | 29-11-14 | D10732 | | 16 | | TB0100Y | C025 | BJ | | ALL |
| 70C | 20 | PA | | | 7-0 | 29-11-14 | D10732 | | 17 | | D04708J | 51 | | | 050-099, 150-199, 275-277, 280-299 |
| 70C | 20 | PA | | | 5-4 | 29-11-14 | D10732 | | 17 | | D04708J | 51 | | | 278 |
| 70D | 20 | PA | | | 4-0 | 29-11-14 | D04708J | | 54 | | D04714J | 46 | | | 050-099, 150-199, 275-277, 280-299 |
| 70D | 20 | PA | | | 3-5 | 29-11-14 | D04708J | | 54 | | D04714J | 46 | | | 278 |
| 70E | 20 | PA | | | 12-0 | 29-11-14 | D05000P | | 35 | | D04714J | 47 | | | 050-099, 150-199, 275-277, 280-299 |
| 70E | 20 | PA | | | 11-11 | 29-11-14 | D05000P | | 35 | | D04714J | 47 | | | 278 |
| 70F | 20 | PA | | | 5-0 | 29-11-14 | D04714J | | 48 | | TB0106Y | A019 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 70F | 20 | PA | | | 4-10 | 29-11-14 | D04714J | | 48 | | TB0106Y | A019 | BJ | | 278 |
| 70W | 18 | PA | | | 5-0 | 38-32-11 | D05064J | | 23 | | TB0100F | A035 | 2 | | 156-157, 166-199, 277, 280-299 |
| 70W | 18 | PA | | | 4-0 | 38-32-11 | D05064J | | 23 | | TB0100F | A035 | 2 | | 278 |
| 70X | 18 | PA | | | 5-0 | 38-32-11 | D05064J | | 24 | DK | TB0100F | C035 | 2 | | 156-157, 166-199, 277, 280-299 |
| 70X | 18 | PA | | | 4-0 | 38-32-11 | D05064J | | 24 | DK | TB0100F | C035 | 2 | | 278 |
| 710 | 22 | PA | | | 13-0 | 30-41-11 | D00876 | | 10 | | D05064J | 9 | | | 050-099, 150-199, 275-277, 280-299 |
| 710 | 22 | PA | | | 12-2 | 30-41-11 | D00876 | | 10 | | D05064J | 9 | | | 278 |
| 711 | 24 | PK | | | 13-0 | 30-41-11 | D00876 | | 11 | | D05064J | 6 | | | 050-099, 150-199, 275-277, 280-299 |
| 711 | 24 | PK | | | 12-2 | 30-41-11 | D00876 | | 11 | | D05064J | 6 | | | 278 |
| 712 | 24 | PK | | | 13-0 | 30-41-11 | D00876 | | 12 | | D05064J | 4 | | | 050-099, 150-199, 275-277, 280-299 |
| 712 | 24 | PK | | | 12-2 | 30-41-11 | D00876 | | 12 | | D05064J | 4 | | | 278 |
| 714 | 24 | PK | | | 11-0 | 78-36-11 | D04714J | | 40 | | TB0098Y | A028 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 714 | 24 | PK | | | 4-7 | 78-36-11 | D04714J | | 40 | | TB0098Y | A028 | BJ | | 278 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 56
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 715 | 22 | PQ | DF | 13-0 | 28-31-12 | D12172 | | 5 | | | D04718J | 20 | | | 050-099, 155-199, 276-277, 280-299 278 |
| 715 | 22 | PQ | DF | 12-8 | 28-31-12 | D12172 | | 5 | | | D04718J | 20 | | | 050-099, 155-199, 276-299 |
| 715Z | | | DF | 0-0 | 28-31-12 | D12172 | | DED | | | D04718J | DED | | | 050-099, 155-199, 276-299 |
| 716 | 20 | PA | | 11-0 | 78-34-11 | GD04428 | | S.. | 2 | | D04718J | | | GE | 050-099, 150-199, 275-277, 280-299 278 |
| 716 | 20 | PA | | 4-11 | 78-34-11 | GD04428 | | S.. | 2 | | D04718J | | | GE | 050-099, 150-199, 275-277, 280-299 278 |
| 720 | 22 | PA | | 13-0 | 28-31-21 | D12174 | | 6 | | | D04708J | 36 | | | 050-099, 155-199, 276-277, 280-299 278 |
| 720 | 22 | PA | | 12-5 | 28-31-21 | D12174 | | 6 | | | D04708J | 36 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 721 | 18 | PA | | 8-0 | 33-13-16 | D00856 | | 1 | DK | | TB0064G | 3 | 2 | | 050-099, 150-199, 275-277, 280-299 278 |
| 721 | 18 | PA | | 8-1 | 33-13-16 | D00856 | | 1 | DK | | TB0064G | 3 | 2 | | 050-099, 150-199, 275-277, 280-299 278 |
| 722 | 18 | PA | | 8-0 | 33-13-16 | D00856 | | 2 | DK | | GD00102 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 278 |
| 722 | 18 | PA | | 7-2 | 33-13-16 | D00856 | | 2 | DK | | GD00102 | A.. | 2 | | 050-099, 155-199, 276-277, 280-299 278 |
| 723 | 22 | PQ | DG | 11-0 | 28-42-12 | TB0070Y | | C020 | BJ | | D05400J | 7 | | | 050-099, 155-199, 276-277, 280-299 278 |
| 723 | 22 | PQ | DG | 11-5 | 28-42-12 | TB0070Y | | C020 | BJ | | D05400J | 7 | | | 050-099, 155-199, 276-299 |
| 723Z | | | DG | 0-0 | 28-42-12 | TB0070Y | | DED | | | D05400J | DED | | | 050-099, 155-199, 276-299 |
| 724 | 22 | PQ | DH | 13-0 | 28-42-12 | TB0066Y | | C020 | BJ | | D04718J | 2 | | | 050-099, 155-199, 276-277, 280-299 278 |
| 724 | 22 | PQ | DH | 10-8 | 28-42-12 | TB0066Y | | C020 | BJ | | D04718J | 2 | | | 050-099, 155-199, 276-299 |
| 724Z | | | DH | 0-0 | 28-42-12 | TB0066Y | | DED | | | D04718J | DED | | | 050-099, 155-199, 276-299 |
| 725 | 20 | PA | | 8-0 | 33-44-21 | D00856 | | 5 | | | D05000P | 20 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 725 | 20 | PA | | 7-7 | 33-44-21 | D00856 | | 5 | | | D05000P | 20 | | | 050-099, 150-199, 275-277, 280-299 278 |
| 726 | 18 | PA | | 14-0 | 33-44-21 | D00856 | | 6 | DK | | D04718J | 16 | DK | | 050-099, 150-199, 275-277, 280-299 278 |
| 726 | 18 | PA | | 13-8 | 33-44-21 | D00856 | | 6 | DK | | D04718J | 16 | DK | | 050-099 |
| 730 | 18 | PA | | 6-0 | 33-42-11 | D00856 | | 10 | DK | | D04968P | 24 | DK | | 150-199, 275-277, 280-299 |
| 730 | 16 | PA | | 6-0 | 33-42-11 | D00856 | | 10 | FM | | D04968P | 24 | FM | | 278 |
| 730 | 16 | PA | | 4-11 | 33-42-11 | D00856 | | 10 | FM | | D04968P | 24 | FM | | 050-099 |
| 731 | 18 | PA | | 8-0 | 33-42-11 | D00856 | | 11 | DK | | D05000P | 25 | DL | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 57

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 731 | 16 | | PA | 8-0 | 33-42-11 | D00856 | | 11 | FM | | | | D05000P | 25 | FL | | 150-199, 275-277, 280-299 |
| 731 | 16 | | PA | 7-7 | 33-42-11 | D00856 | | 11 | FM | | | | D05000P | 25 | FL | | 278 |
| 732 | 24 | | PK | 8-0 | 33-42-11 | D00856 | | 12 | | | | | TB0070Y | C015 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 732 | 24 | | PK | 7-10 | 33-42-11 | D00856 | | 12 | | | | | TB0070Y | C015 | BJ | | 278 |
| 734 | 22 | | PQ | DI | 13-0 | 28-42-13 | D12172 | | 6 | | | | D04718J | 21 | | | 050-099, 155-199, 276-277, 280-299 |
| 734 | 22 | | PQ | DI | 12-8 | 28-42-13 | D12172 | | 6 | | | | D04718J | 21 | | | 278 |
| 734Z | | | | DI | 0-0 | 28-42-13 | D12172 | | DED | | | | D04718J | DED | | | 050-099, 155-199, 276-299 |
| 735 | 24 | | PK | 6-0 | 33-42-11 | D00856 | | 15 | | | | | D04968P | 15 | | | 050-099, 150-199, 275-277, 280-299 |
| 735 | 24 | | PK | 4-11 | 33-42-11 | D00856 | | 15 | | | | | D04968P | 15 | | | 278 |
| 738 | 20 | | PA | 8-0 | 33-43-11 | D00856 | | 18 | | | | | TB0066X | D006 | BJ | | 050-099 |
| 738 | 18 | | PA | 8-0 | 33-43-11 | D00856 | | 18 | DK | | | | TB0066F | A026 | 2 | | 150-199, 275-277, 280-299 |
| 738 | 18 | | PA | 8-1 | 33-43-11 | D00856 | | 18 | DK | | | | TB0066F | A026 | 2 | | 278 |
| 739 | 20 | | PA | 8-0 | 33-43-11 | D00856 | | 19 | | | | | TB0066X | C006 | BJ | | 050-099 |
| 739 | 18 | | PA | 8-0 | 33-43-11 | D00856 | | 19 | DK | | | | TB0066F | A025 | 2 | | 150-199, 275-277, 280-299 |
| 739 | 18 | | PA | 8-1 | 33-43-11 | D00856 | | 19 | DK | | | | TB0066F | A025 | 2 | | 278 |
| 740 | 20 | | PA | 13-0 | 28-31-11 | D12174 | | 3 | | | | | D04708J | 24 | | | 050-099, 155-199, 276-277, 280-299 |
| 740 | 20 | | PA | 12-5 | 28-31-11 | D12174 | | 3 | | | | | D04708J | 24 | | | 278 |
| 742 | 20 | | PA | 13-0 | 28-31-11 | D12174 | | 4 | | | | | D04708J | 31 | | | 050-099, 155-199, 276-277, 280-299 |
| 742 | 20 | | PA | 12-5 | 28-31-11 | D12174 | | 4 | | | | | D04708J | 31 | | | 278 |
| 743 | 20 | | PA | 12-0 | 28-31-12 | D12174 | | 10 | | | | | D07960J | 21 | | | 050-099 |
| 743 | 20 | | PA | 11-0 | 28-31-12 | D12174 | | 10 | | | | | D07960J | 21 | | | 155-199, 276-277, 280-299 |
| 743 | 20 | | PA | 11-6 | 28-31-12 | D12174 | | 10 | | | | | D07960J | 21 | | | 278 |
| 744 | 20 | | PA | 13-0 | 28-31-12 | D12174 | | 11 | | | | | D04718J | 17 | | | 050-099, 155-199, 276-277, 280-299 |
| 744 | 20 | | PA | 12-8 | 28-31-12 | D12174 | | 11 | | | | | D04718J | 17 | | | 278 |
| 745 | 20 | | PA | 13-0 | 28-31-12 | D12174 | | 12 | | | | | D04718J | 3 | | | 050-099, 155-199, 276-277, 280-299 |
| 745 | 20 | | PA | 12-8 | 28-31-12 | D12174 | | 12 | | | | | D04718J | 3 | | | 278 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 58

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 746 | 20 | PQ | CA | 7-0 | 28-31-12 | D12174 | | 9 | | | | TB0070Y | C022 | BJ | 050-099, 155-199, 277, 280-299 | |
| 746 | 20 | PQ | CA | 6-10 | 28-31-12 | D12174 | | 9 | | | | TB0070Y | C022 | BJ | 278 | |
| 746Z | | | CA | 0-0 | 28-31-12 | D12174 | | DED | | | | TB0070Y | DED | | 050-099, 155-199, 277-299 | |
| 747 | 20 | PQ | CB | 6-0 | 28-31-12 | D12174 | | 1 | | | | GD00263 | S.. | 2 | 050-099, 155-199, 277, 280-299 | |
| 747 | 20 | PQ | CB | 5-4 | 28-31-12 | D12174 | | 1 | | | | GD00263 | S.. | 2 | 278 | |
| 747Z | | | CB | 0-0 | 28-31-12 | D12174 | | DED | | | | GD00263 | DED | | 050-099, 155-199, 277-299 | |
| 748 | 20 | PQ | BP | 13-0 | 28-31-12 | D04718J | | 13 | | | | TB0070Y | C022 | BJ | 050-099, 155-199, 277, 280-299 | |
| 748 | 20 | PQ | BP | 12-2 | 28-31-12 | D04718J | | 13 | | | | TB0070Y | C022 | BJ | 278 | |
| 748Z | | | BP | 0-0 | 28-31-12 | D04718J | | DED | | | | TB0070Y | DED | | 050-099, 155-199, 277-299 | |
| 75A | 22 | PA | | 8-0 | 33-45-11 | D00874 | | 21 | | | | TB0066X | A003 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 75A | 22 | PA | | 8-3 | 33-45-11 | D00874 | | 21 | | | | TB0066X | A003 | BJ | 278 | |
| 75B | 20 | PA | | 8-0 | 33-45-11 | D00874 | | 22 | | | | GD00265 | A.. | 2 | 050-099, 150-199, 275-277, 280-299 | |
| 75B | 20 | PA | | 7-5 | 33-45-11 | D00874 | | 22 | | | | GD00265 | A.. | 2 | 278 | |
| 75M | 22 | PA | | 4-0 | 21-66-11 | D05726J | | 11 | | | | D05180J | 36 | | 050-099, 162-199 | |
| 75N | 22 | PA | | 6-0 | 21-66-21 | TB0102Y | A039 | BJ | | | | D05652J | 8 | | 050-099 | |
| 75N | 22 | PA | | 5-0 | 21-66-21 | D05652J | | 8 | | | | TB0102Y | A039 | BJ | 162-199 | |
| 770 | 22 | PA | | 3-0 | 24-25-11 | D07962J | | 18 | | | | TB0102X | D002 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 770 | 22 | PA | | 3-2 | 24-25-11 | D07962J | | 18 | | | | TB0102X | D002 | BJ | 278 | |
| 771 | 22 | PQ | FA | 7-0 | 24-25-11 | D10222 | | 24 | | | | TB0106Y | A014 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 771 | 22 | PQ | FA | 6-7 | 24-25-11 | D10222 | | 24 | | | | TB0106Y | A014 | BJ | 278 | |
| 771Z | | | FA | 0-0 | 24-25-11 | D10222 | | DED | | | | TB0106Y | DED | | ALL | |
| 772 | 22 | PQ | TS | 14-0 | 22-21-21 | D10222 | | 2 | | | | TB0070X | A009 | BJ | 050-099, 150-199, 275-277, 280-299 | |
| 772 | 22 | PQ | TS | 13-6 | 22-21-21 | D10222 | | 2 | | | | TB0070X | A009 | BJ | 278 | |
| 772Z | | | TS | 0-0 | 22-21-21 | D10222 | | DED | | | | TB0070X | DED | | ALL | |
| 773 | 20 | PA | | 8-0 | 28-43-11 | D10222 | | 3 | | | | GD04428 | D.. | 2 | 050-099, 150-199, 275-277, 280-299 | |
| 773 | 20 | PA | | 6-8 | 28-43-11 | D10222 | | 3 | | | | GD04428 | D.. | 2 | 278 | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 59

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 774 | 20 | | PA | 7-0 | 24-31-11 | D10222 | | 26 | | GD04428 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 | |
| 774 | 20 | | PA | 6-8 | 24-31-11 | D10222 | | 26 | | GD04428 | D.. | 2 | | 278 | |
| 775R | 20 | | PH | 6-0 | 26-18-11 | D10222 | | 5 | | D04730J | | 8 | | 050-099, 150-199, 275-277, 280-299 | |
| 775R | 20 | | PH | 6-8 | 26-18-11 | D10222 | | 5 | | D04730J | | 8 | | 278 | |
| 776R | 22 | | PH | 6-0 | 26-18-11 | D04726J | | 21 | | D10222 | | 6 | | 050-099 | |
| 776R | 22 | | PH | 7-0 | 26-18-11 | D04726J | | 21 | | D10222 | | 6 | | 150-199, 275-277, 280-299 | |
| 776R | 22 | | PH | 4-11 | 26-18-11 | D04726J | | 21 | | D10222 | | 6 | | 278 | |
| 777R | 22 | | PH | 6-0 | 26-18-11 | D04644J | | 29 | | D10222 | | 7 | | 050-099 | |
| 777R | 22 | | PH | 5-0 | 26-18-11 | D04644J | | 29 | | D10222 | | 7 | | 150-199, 275-277, 280-299 | |
| 777R | 22 | | PH | 4-8 | 26-18-11 | D04644J | | 29 | | D10222 | | 7 | | 278 | |
| 778 | 24 | | PK | 7-0 | 24-31-11 | D10222 | | 27 | | TB0106Y | A026 | BJ | | 050-099, 150-199, 275-277, 280-299 | |
| 778 | 24 | | PK | 6-7 | 24-31-11 | D10222 | | 27 | | TB0106Y | A026 | BJ | | 278 | |
| 779 | 22 | | PQ | 6-0 | 24-25-11 | D10222 | | 25 | | TB0102X | D006 | BJ | | 050-099, 150-199, 275-277, 280-299 | |
| 779 | 22 | | PQ | 6-5 | 24-25-11 | D10222 | | 25 | | TB0102X | D006 | BJ | | 278 | |
| 779Z | | | FB | 0-0 | 24-25-11 | D10222 | | DED | | TB0102X | DED | | | ALL | |
| 780 | 24 | | PK | 6-0 | 30-41-11 | D10222 | | 10 | | D05064J | | 2 | | 050-099, 150-199, 275-277, 280-299 | |
| 780 | 24 | | PK | 4-0 | 30-41-11 | D10222 | | 10 | | D05064J | | 2 | | 278 | |
| 781 | 24 | | PK | 5-0 | 30-31-11 | D10222 | | 11 | | D05726J | | 46 | | 050-099, 150-199, 275-277, 280-299 | |
| 781 | 24 | | PK | 4-7 | 30-31-11 | D10222 | | 11 | | D05726J | | 46 | | 278 | |
| 784 | 24 | | PV | 6-0 | 21-58-11 | D10222 | | 14 | | TB0102X | D001 | BJ | | 050-099, 150-199, 275-277, 280-299 | |
| 784 | 24 | | PV | 6-5 | 21-58-11 | D10222 | | 14 | | TB0102X | D001 | BJ | | 278 | |
| 784Z | | | SU | 0-0 | 21-58-11 | D10222 | | DED | | TB0102X | DED | | | ALL | |
| 785 | 24 | | PV | 6-0 | 21-58-11 | D10222 | | 15 | | TB0102X | C001 | BJ | | 050-099, 150-199, 275-277, 280-299 | |
| 785 | 24 | | PV | 6-5 | 21-58-11 | D10222 | | 15 | | TB0102X | C001 | BJ | | 278 | |
| 785Z | | | SV | 0-0 | 21-58-11 | D10222 | | DED | | TB0102X | DED | | | ALL | |
| 786R | 22 | | PH | 6-0 | 26-18-31 | D04644J | | 33 | | D10222 | | 16 | | 050-099 | |
| 786R | 22 | | PH | 5-0 | 26-18-31 | D04644J | | 33 | | D10222 | | 16 | | 150-199, 275-277, 280-299 | |
| 786R | 22 | | PH | 4-8 | 26-18-31 | D04644J | | 33 | | D10222 | | 16 | | 278 | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 60

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 787R | 22 | | PH | 6-0 | 26-18-31 | TB0098X | A006 | BJ | | D10222 | | 17 | | | 050-099 | |
| 787R | 22 | | PH | 7-0 | 26-18-31 | D10222 | | 17 | | TB0098X | A006 | BJ | | | 150-199, 275-277, 280-299 | |
| 787R | 22 | | PH | 6-4 | 26-18-31 | D10222 | | 17 | | TB0098X | A006 | BJ | | | 278 | |
| 788R | 22 | | PH | 6-0 | 26-18-21 | D05726J | | 61 | | D10222 | | 18 | | | 050-099, 150-199, 275-277, 280-299 | |
| 788R | 22 | | PH | 4-7 | 26-18-21 | D05726J | | 61 | | D10222 | | 18 | | | 278 | |
| 789R | 22 | | PH | 6-0 | 26-18-11 | D04726J | | 41 | | D10222 | | 19 | | | 050-099 | |
| 789R | 22 | | PH | 7-0 | 26-18-11 | D04726J | | 41 | | D10222 | | 19 | | | 150-199, 275-277, 280-299 | |
| 789R | 22 | | PH | 4-11 | 26-18-11 | D04726J | | 41 | | D10222 | | 19 | | | 278 | |
| 792 | 22 | | PQ TA | 6-0 | 30-11-11 | D10222 | | 22 | | TB0102X | B005 | BJ | | | 050-099, 150-199, 275-277, 280-299 | |
| 792 | 22 | | PQ TA | 6-5 | 30-11-11 | D10222 | | 22 | | TB0102X | B005 | BJ | | | 278 | |
| 792Z | | | TA | 0-0 | 30-11-11 | D10222 | DED | | | TB0102X | DED | | | | ALL | |
| 793 | 22 | | PQ TB | 7-0 | 30-11-11 | D10222 | | 23 | | GD04426 | D.. | 2 | | | 050-099, 155-199 | |
| 793 | 22 | | PQ TB | 8-0 | 30-11-11 | D10222 | | 23 | | GD04426 | D.. | 2 | | | 150-154 | |
| 793 | 22 | | PQ TB | 6-0 | 30-11-11 | D10222 | | 23 | | TB0102Z | | 19 | BJ | | 275-277, 280-299 | |
| 793 | 22 | | PQ TB | 6-5 | 30-11-11 | D10222 | | 23 | | TB0102Z | | 19 | BJ | | 278 | |
| 793Z | | | TB | 0-0 | 30-11-11 | D10222 | DED | | | GD04426 | DED | | | | 050-099, 150-199 | |
| 793Z | | | TB | 0-0 | 30-11-11 | D10222 | DED | | | TB0102Z | DED | | | | 275-299 | |
| 799R | 22 | | PH | 6-0 | 26-18-31 | D04644J | | 35 | | D10222 | | 29 | | | 050-099 | |
| 799R | 22 | | PH | 5-0 | 26-18-31 | D04644J | | 35 | | D10222 | | 29 | | | 150-199, 275-277, 280-299 | |
| 799R | 22 | | PH | 4-8 | 26-18-31 | D04644J | | 35 | | D10222 | | 29 | | | 278 | |
| 79A | 20 | | PA | 5-0 | 30-81-11 | D07960J | | 22 | | D04714J | | 20 | | | 050-099, 155-199 | |
| 79A | 20 | | PA | 6-0 | 30-81-11 | D07960J | | 22 | | D04714J | | 20 | | | 150-154 | |
| 79C | 20 | | PA | 6-0 | 30-81-11 | D12206 | | 5 | | D04714J | | 26 | | | 050-099, 155-199 | |
| 79C | 20 | | PA | 7-0 | 30-81-11 | D12206 | | 5 | | D04714J | | 26 | | | 150-154 | |
| 79D | 20 | | PA | 8-0 | 30-81-11 | D12206 | | 6 | | GD04426 | D.. | 2 | | | 050-099, 155-199 | |
| 79D | 20 | | PA | 9-0 | 30-81-11 | D12206 | | 6 | | GD04426 | D.. | 2 | | | 150-154 | |
| 79E | 20 | | PA | 13-0 | 30-81-11 | D12206 | | 7 | | TB0066X | C003 | BJ | | | 050-099, 155-199 | |
| 79E | 20 | | PA | 14-0 | 30-81-11 | D12206 | | 7 | | TB0066X | C003 | BJ | | | 150-154 | |
| 79F | 20 | | PA | 14-0 | SPARE | D00888 | CAP | Y | | D04714J | | 32 | | | 050-099, 155-199 | |
| 79G | 20 | | PA | 8-0 | SPARE | D00888 | CAP | Y | | GD00100 | D.. | 2 | | | 050-099 | |
| 79G | 20 | | PA | 7-0 | SPARE | D00888 | CAP | Y | | GD00100 | D.. | 2 | | | 155-199 | |
| 800R | 22 | | PH | 6-0 | 26-18-21 | D04644J | | 31 | | D10222 | | 30 | | | 050-099 | |
| 800R | 22 | | PH | 5-0 | 26-18-21 | D04644J | | 31 | | D10222 | | 30 | | | 150-199, 275-277, 280-299 | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 61

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 800R | 22 | | PH | | 4-8 | 26-18-21 | D04644J | | 31 | | D10222 | | 30 | | 278 |
| 801R | 22 | | PH | | 6-0 | 26-18-21 | D04708J | | 41 | | D10222 | | 31 | | 050-099 |
| 801R | 22 | | PH | | 5-0 | 26-18-21 | D04708J | | 41 | | D10222 | | 31 | | 150-199, 275-277, 280-299 |
| 801R | 22 | | PH | | 4-9 | 26-18-21 | D04708J | | 41 | | D10222 | | 31 | | 278 |
| 802 | 22 | | PQ | TP | 7-0 | 27-13-11 | D10112 | | 1 | | TB0100Y | A033 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 802 | 22 | | PQ | TP | 6-8 | 27-13-11 | D10112 | | 1 | | TB0100Y | A033 | BJ | | 278 |
| 802Z | | | | TP | 0-0 | 27-13-11 | D10112 | | DED | | TB0100Y | DED | | | ALL |
| 803 | 22 | | PQ | SA | 7-0 | 33-16-26 | TB0098Y | | C035 | BJ | D10112 | | 3 | | 050-099, 150-199, 275-277, 280-299 |
| 803 | 22 | | PQ | SA | 6-8 | 33-16-26 | TB0098Y | | C035 | BJ | D10112 | | 3 | | 278 |
| 803Z | | | | SA | 0-0 | 33-16-26 | TB0098Y | | DED | | D10112 | | DED | | ALL |
| 804 | 22 | | PA | | 7-0 | 33-16-26 | TB0098Z | | 38 | BJ | D10112 | | 4 | | 050-099, 150-199, 275-277, 280-299 |
| 804 | 22 | | PA | | 6-8 | 33-16-26 | TB0098Z | | 38 | BJ | D10112 | | 4 | | 278 |
| 805 | 20 | | PQ | TO | 6-0 | 27-13-11 | D10112 | | 5 | | D04714J | | 28 | | 050-099, 150-199, 275-277, 280-299 |
| 805 | 20 | | PQ | TO | 4-10 | 27-13-11 | D10112 | | 5 | | D04714J | | 28 | | 278 |
| 805Z | | | | TO | 0-0 | 27-13-11 | D10112 | | DED | | D04714J | | DED | | ALL |
| 806 | 20 | | PQ | TN | 6-0 | 27-13-11 | D10112 | | 6 | | D04714J | | 27 | | 050-099, 150-199, 275-277, 280-299 |
| 806 | 20 | | PQ | TN | 4-10 | 27-13-11 | D10112 | | 6 | | D04714J | | 27 | | 278 |
| 806Z | | | | TN | 0-0 | 27-13-11 | D10112 | | DED | | D04714J | | DED | | ALL |
| 807 | 20 | | PQ | TM | 6-0 | 27-13-11 | D10112 | | 7 | | D07970J | | 10 | | ALL |
| 807Z | | | | TM | 0-0 | 27-13-11 | D10112 | | DED | | D07970J | | DED | | ALL |
| 80A | 18 | | PA | | 7-0 | 33-13-21 | D00551 | | 1 | DK | TB0096G | | 30 | 2 | 050-099 |
| 80A | 18 | | PA | | 8-0 | 33-13-21 | D00551 | | 1 | DK | TB0096G | | 30 | 2 | 150-199, 275-277, 280-299 |
| 80A | 18 | | PA | | 7-5 | 33-13-21 | D00551 | | 1 | DK | TB0096G | | 30 | 2 | 278 |
| 80B | 18 | | PA | | 8-0 | 33-13-21 | D00551 | | 2 | DK | GD04428 | | A.. | 2 | 050-099, 150-199, 275-277, 280-299 |
| 80B | 18 | | PA | | 7-4 | 33-13-21 | D00551 | | 2 | DK | GD04428 | | A.. | 2 | 278 |
| 80C | 22 | | PA | | 8-0 | 23-51-41 | D00551 | | 3 | | D07966J | | 5 | | 050-099, 150-199, 275-277, 280-299 |
| 80C | 22 | | PA | | 6-0 | 23-51-41 | D00551 | | 3 | | D07966J | | 5 | | 278 |
| 80D | 20 | | PA | | 8-0 | 23-51-41 | D00551 | | 4 | | GD04426 | | D.. | 2 | 050-099, 150-199, 275-277, 280-299 |
| 80D | 20 | | PA | | 7-6 | 23-51-41 | D00551 | | 4 | | GD04426 | | D.. | 2 | 278 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 62

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 80J | 24 | PV | RJ | 6-0 | 23-51-41 | D00551 | | 9 | | | D01377 | A | | 050-099, 150-199, 275-277, 280-299 | |
| 80J | 24 | PV | RJ | 5-4 | 23-51-41 | D00551 | | 9 | | | D01377 | A | | 278 | |
| 80JZ | | | RJ | 0-0 | 23-51-41 | D00551 | | 8 | | | D01377 | B | | ALL | |
| 80S | 24 | PV | RK | 6-0 | 23-51-41 | D00551 | | 16 | | | D00557 | 16 | | 050-099 | |
| 80S | 24 | PV | RK | 5-0 | 23-51-41 | D00551 | | 16 | | | D00557 | 16 | | 150-199, 275-277, 280-299 | |
| 80S | 24 | PV | RK | 4-0 | 23-51-41 | D00551 | | 16 | | | D00557 | 16 | | 278 | |
| 80SZ | | | RK | 0-0 | 23-51-41 | D00551 | | 15 | | | D00557 | 17 | | ALL | |
| 80V | 16 | PA | | 4-0 | 73-21-11 | D07966J | | 4 | FL | | D04720J | 16 | FM | 050-099, 155-199, 277, 280-299 | |
| 80V | 16 | PA | | 6-0 | 73-21-11 | D07966J | | 4 | FL | | D04720J | 16 | FM | 150-154 | |
| 80V | 16 | PA | | 1-0 | 73-21-11 | D07966J | | 4 | FL | | D04720J | 16 | FM | 275-276 | |
| 80V | 16 | PA | | 2-9 | 73-21-11 | D07966J | | 4 | FL | | D04720J | 16 | FM | 278 | |
| 80Z | 24 | PK | | 2-0 | 23-51-41 | D00551 | | 23 | | | D00551 | 24 | | 050-099, 150-199, 275-277, 280-299 | |
| 80Z | 24 | PK | | 0-7 | 23-51-41 | D00551 | | 23 | | | D00551 | 24 | | 278 | |
| 811 | 22 | PA | | 6-0 | 27-23-11 | D10110 | | 11 | | | D04730J | 3 | | 050-099, 150-199, 275-277, 280-299 | |
| 811 | 22 | PA | | 4-4 | 27-23-11 | D10110 | | 11 | | | D04730J | 3 | | 278 | |
| 813 | 22 | PQ | TW | 8-0 | 33-16-26 | TB0106Z | | 37 | BJ | | D10112 | 13 | | 050-099, 150-199, 275-277, 280-299 | |
| 813 | 22 | PQ | TW | 6-11 | 33-16-26 | TB0106Z | | 37 | BJ | | D10112 | 13 | | 278 | |
| 813Z | | | TW | 0-0 | 33-16-26 | TB0106Z | | DED | | | D10112 | DED | | ALL | |
| 814 | 22 | PQ | TV | 8-0 | 33-16-26 | TB0106Z | | 38 | BJ | | D10112 | 14 | | 050-099, 150-199, 275-277, 280-299 | |
| 814 | 22 | PQ | TV | 6-11 | 33-16-26 | TB0106Z | | 38 | BJ | | D10112 | 14 | | 278 | |
| 814Z | | | TV | 0-0 | 33-16-26 | TB0106Z | | DED | | | D10112 | DED | | ALL | |
| 815 | 20 | PA | | 6-0 | 27-23-11 | D10110 | | 15 | | | D04730J | 2 | | 050-099, 150-199, 275-277, 280-299 | |
| 815 | 20 | PA | | 4-4 | 27-23-11 | D10110 | | 15 | | | D04730J | 2 | | 278 | |
| 816 | 20 | PA | | 6-0 | 27-23-11 | D10110 | | 16 | | | D04730J | 1 | | 050-099, 150-199, 275-277, 280-299 | |
| 816 | 20 | PA | | 4-4 | 27-23-11 | D10110 | | 16 | | | D04730J | 1 | | 278 | |
| 817 | 20 | PA | | 6-0 | 27-23-11 | D10110 | | 17 | | | D07968J | 11 | | ALL | |
| 81A | 20 | PA | | 6-0 | 23-51-41 | D01377 | | F | | | GD04426 | D.. | 2 | 050-099, 150-199, 275-277, 280-299 | |
| 81A | 20 | PA | | 4-7 | 23-51-41 | D01377 | | F | | | GD04426 | D.. | 2 | 278 | |
| 81B | 24 | PK | | 7-0 | 23-51-41 | D01377 | | E | | | D00551 | 31 | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 63

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 81B | 24 | | PK | 6-0 | 23-51-41 | D01377 | | E | | | | | D00551 | 31 | | | 150-199, 275-277, 280-299 |
| 81B | 24 | | PK | 5-4 | 23-51-41 | D01377 | | E | | | | | D00551 | 31 | | | 278 |
| 81C | 24 | | PK | 7-0 | 23-51-41 | D00557 | | 7 | | | | | SM00010 | | 9 | | 050-099, 150-199, 275-277, 280-299 |
| 81C | 24 | | PK | 6-2 | 23-51-41 | D00557 | | 7 | | | | | SM00010 | | 9 | | 278 |
| 81D | 18 | | PA | 8-0 | 33-13-21 | TB0096G | | 30 | 2 | | | | D00557 | 1 | DK | | 050-099 |
| 81D | 18 | | PA | 7-0 | 33-13-21 | D00557 | | 1 | DK | | | | TB0096G | 30 | 2 | | 150-199, 275-277, 280-299 |
| 81D | 18 | | PA | 8-2 | 33-13-21 | D00557 | | 1 | DK | | | | TB0096G | 30 | 2 | | 278 |
| 81E | 18 | | PA | 8-0 | 33-13-21 | GD04426 | | A.. | 2 | | | | D00557 | 2 | DK | | 050-099 |
| 81E | 18 | | PA | 9-0 | 33-13-21 | D00557 | | 2 | DK | | | | GD04426 | A.. | 2 | | 150-199, 275-277, 280-299 |
| 81E | 18 | | PA | 8-3 | 33-13-21 | D00557 | | 2 | DK | | | | GD04426 | A.. | 2 | | 278 |
| 81G | 24 | | PV RL | 7-0 | 23-51-41 | D00551 | | 26 | | | | | D04955J | 4 | | | 050-099, 275-277, 280-299 |
| 81G | 24 | | PV RL | 6-0 | 23-51-41 | D00551 | | 26 | | | | | D04955J | 4 | | | 150-199 |
| 81G | 24 | | PV RL | 5-4 | 23-51-41 | D00551 | | 26 | | | | | D04955J | 4 | | | 278 |
| 81GZ | | | RL | 0-0 | 23-51-41 | D00551 | | 25 | | | | | D04955J | 5 | | | ALL |
| 81J | 20 | | PA | 8-0 | 23-51-41 | D00557 | | 11 | | | | | GD04426 | A.. | 2 | | 050-099 |
| 81J | 20 | | PA | 9-0 | 23-51-41 | D00557 | | 11 | | | | | GD04426 | A.. | 2 | | 150-199, 275-277, 280-299 |
| 81J | 20 | | PA | 8-3 | 23-51-41 | D00557 | | 11 | | | | | GD04426 | A.. | 2 | | 278 |
| 81K | 24 | | PK | 6-0 | 23-51-41 | D00551 | | 29 | | | | | SM00010 | | 9 | | 050-099, 153-199, 275-277, 280-299 |
| 81K | 24 | | PK | 4-11 | 23-51-41 | D00551 | | 29 | | | | | SM00010 | | 9 | | 278 |
| 81L | 24 | | PK | 2-0 | 23-51-41 | D04955J | | 3 | | | | | SM00010 | | 9 | | 050-099, 150-199, 275-277, 280-299 |
| 81L | 24 | | PK | 1-11 | 23-51-41 | D04955J | | 3 | | | | | SM00010 | | 9 | | 278 |
| 820 | 22 | | PA | 6-0 | 30-21-11 | D00888 | | 6 | | | | | D04968P | 16 | | | 050-099, 155-199 |
| 820 | 22 | | PA | 7-0 | 30-21-11 | D00888 | | 6 | | | | | D04968P | 16 | | | 150-154 |
| 821 | 22 | | PA | 6-0 | 27-13-11 | D10110 | | 1 | | | | | D04730J | 6 | | | 050-099, 150-199, 275-277, 280-299 |
| 821 | 22 | | PA | 4-4 | 27-13-11 | D10110 | | 1 | | | | | D04730J | 6 | | | 278 |
| 822 | 24 | | PK | 8-0 | 24-22-41 | D10112 | | 22 | | | | | TB0096X | A001 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 822 | 24 | | PK | 7-1 | 24-22-41 | D10112 | | 22 | | | | | TB0096X | A001 | BJ | | 278 |
| 823 | 22 | | PA | 7-0 | 33-16-26 | TB0098Y | | A035 | BJ | | | | D10110 | 3 | | | 050-099, 150-199, 275-277, 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 64
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 823 | 22 | | PA | 6-10 | 33-16-26 | TB0098Y | A035 | BJ | | D10110 | | 3 | | | 278 | |
| 824 | 22 | | PA | 7-0 | 33-16-26 | TB0098Z | | BJ | | D10110 | | 4 | | | 050-099, 150-199, 275-277, 280-299 | |
| 824 | 22 | | PA | 6-10 | 33-16-26 | TB0098Z | | BJ | | D10110 | | 4 | | | 278 | |
| 825 | 20 | | PA | 6-0 | 27-13-11 | D10110 | | | 5 | D04730J | | 5 | | | 050-099, 150-199, 275-277, 280-299 | |
| 825 | 20 | | PA | 4-4 | 27-13-11 | D10110 | | | 5 | D04730J | | 5 | | | 278 | |
| 826 | 20 | | PA | 6-0 | 27-13-11 | D10110 | | | 6 | D04730J | | 4 | | | 050-099, 150-199, 275-277, 280-299 | |
| 826 | 20 | | PA | 4-4 | 27-13-11 | D10110 | | | 6 | D04730J | | 4 | | | 278 | |
| 827 | 20 | | PA | 6-0 | 27-13-11 | D10110 | | | 7 | D07968J | | 10 | | | ALL | |
| 830 | 24 | | PK | 7-0 | 24-11-11 | D10110 | | | 10 | TB0100Y | A034 | BJ | | | 050-099, 150-199, 275-277, 280-299 | |
| 830 | 24 | | PK | 6-9 | 24-11-11 | D10110 | | | 10 | TB0100Y | A034 | BJ | | | 278 | |
| 831 | 22 | | PQ AZ | 6-0 | 27-23-11 | D10112 | | | 11 | D04720J | | 22 | | | 050-099, 150-199, 275-277, 280-299 | |
| 831 | 22 | | PQ AZ | 4-5 | 27-23-11 | D10112 | | | 11 | D04720J | | 22 | | | 278 | |
| 831Z | | | | 0-0 | 27-23-11 | D10112 | DED | | | D04720J | | DED | | | ALL | |
| 832 | 20 | | PA | 8-0 | 24-11-11 | D10110 | | | 12 | GD04428 | | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 | |
| 832 | 20 | | PA | 7-1 | 24-11-11 | D10110 | | | 12 | GD04428 | | D.. | 2 | | 278 | |
| 835 | 20 | | PQ BZ | 6-0 | 27-23-11 | D10112 | | | 15 | D04720J | | 23 | | | 050-099, 150-199, 275-277, 280-299 | |
| 835 | 20 | | PQ BZ | 4-5 | 27-23-11 | D10112 | | | 15 | D04720J | | 23 | | | 278 | |
| 835Z | | | | 0-0 | 27-23-11 | D10112 | DED | | | D04720J | | DED | | | ALL | |
| 836 | 20 | | PQ CZ | 6-0 | 27-23-11 | D10112 | | | 16 | D04720J | | 21 | | | 050-099, 150-199, 275-277, 280-299 | |
| 836 | 20 | | PQ CZ | 4-5 | 27-23-11 | D10112 | | | 16 | D04720J | | 21 | | | 278 | |
| 836Z | | | | 0-0 | 27-23-11 | D10112 | DED | | | D04720J | | DED | | | ALL | |
| 837 | 20 | | PQ DZ | 6-0 | 27-23-11 | D10112 | | | 17 | D07970J | | 11 | | | ALL | |
| 837Z | | | | 0-0 | 27-23-11 | D10112 | DED | | | D07970J | | DED | | | ALL | |
| 841 | 22 | | PA | 7-0 | SPARE | D04968P | | | 19 | TB0070Y | A017 | BJ | | | 050-099, 155-199 | |
| 841 | 22 | | PA | 8-0 | 30-21-11 | D00888 | | | 1 | TB0070Y | A017 | BJ | | | 275-277, 280-299 | |
| 841 | 22 | | PA | 7-9 | 30-21-11 | D00888 | | | 1 | TB0070Y | A017 | BJ | | | 278 | |
| 842 | 22 | | PA | 13-0 | 30-11-11 | D00888 | | | 2 | TB0102X | A005 | BJ | | | 275-277, 280-299 | |
| 842 | 22 | | PA | 12-11 | 30-11-11 | D00888 | | | 2 | TB0102X | A005 | BJ | | | 278 | |
| 843 | 22 | | PQ FC | 8-0 | 33-16-17 | TB0070Y | C021 | BJ | | D00888 | | 3 | | | 050-099, 150-199 | |
| 843 | 22 | | PQ FC | 8-0 | 33-16-17 | TB0068Y | A019 | BJ | | D00888 | | 3 | | | 275-277, 280-299 | |
| 843 | 22 | | PQ FC | 7-9 | 33-16-17 | TB0068Y | A019 | BJ | | D00888 | | 3 | | | 278 | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 65

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 843Z | | | | FC | 0-0 | 33-16-17 | D00888 | DED | | | TB0070Y | DED | | | 050-099, 150-199 |
| 843Z | | | | FC | 0-0 | 33-16-17 | D00888 | DED | | | TB0068Y | DED | | | 275-299 |
| 844 | 22 | PA | | | 8-0 | 33-16-17 | TB0068Z | 22 | BJ | | D00888 | 4 | | | 050-099, 150-199, 275-277, 280-299 |
| 844 | 22 | PA | | | 7-9 | 33-16-17 | TB0068Z | 22 | BJ | | D00888 | 4 | | | 278 |
| 847 | 24 | PK | | | 8-0 | 30-21-11 | TB0070Y | A018 | BJ | | D05000P | 31 | | | 050-099, 150-154 |
| 847 | 24 | PK | | | 4-0 | 30-21-11 | TB0070Y | A018 | BJ | | D05000P | 31 | | | 155-199 |
| 847 | 24 | PK | | | 8-0 | 30-21-11 | D00888 | 7 | | | D05000P | 31 | | | 275-277, 280-299 |
| 847 | 24 | PK | | | 7-6 | 30-21-11 | D00888 | 7 | | | D05000P | 31 | | | 278 |
| 848 | 24 | PK | | | 8-0 | 30-21-11 | D00888 | 8 | | | TB0070Y | A018 | BJ | | 275-277, 280-299 |
| 848 | 24 | PK | | | 7-9 | 30-21-11 | D00888 | 8 | | | TB0070Y | A018 | BJ | | 278 |
| 849 | 24 | PK | | | 14-0 | 73-21-16 | D00888 | 9 | | | D04710J | 49 | | | 275-277, 280-299 |
| 849 | 24 | PK | | | 13-10 | 73-21-16 | D00888 | 9 | | | D04710J | 49 | | | 278 |
| 850 | 20 | PA | | | 8-0 | 73-21-16 | D00888 | 10 | | | GD00102 | D.. | 2 | | 275-277, 280-299 |
| 850 | 20 | PA | | | 7-1 | 73-21-16 | D00888 | 10 | | | GD00102 | D.. | 2 | | 278 |
| 851 | 22 | PA | | | 6-0 | 30-21-11 | D00888 | 2 | | | D04968P | 6 | | | 050-099, 150-199 |
| 851 | 22 | PA | | | 6-0 | 30-21-11 | D00888 | 11 | | | D04968P | 6 | | | 275-277, 280-299 |
| 851 | 22 | PA | | | 4-10 | 30-21-11 | D00888 | 11 | | | D04968P | 6 | | | 278 |
| 852 | 22 | PA | | | 7-0 | 30-21-11 | D00888 | 16 | | | TB0070Y | A017 | BJ | | 050-099 |
| 852 | 22 | PA | | | 8-0 | 30-21-11 | D00888 | 16 | | | TB0070Y | A017 | BJ | | 150-199 |
| 852 | 22 | PA | | | 8-0 | 30-21-11 | D00888 | 12 | | | TB0070Y | A017 | BJ | | 275-277, 280-299 |
| 852 | 22 | PA | | | 7-9 | 30-21-11 | D00888 | 12 | | | TB0070Y | A017 | BJ | | 278 |
| 853 | 22 | PA | | | 6-0 | 30-21-11 | D00888 | 13 | | | D04968P | 5 | | | 050-099, 150-199, 275-277, 280-299 |
| 853 | 22 | PA | | | 4-10 | 30-21-11 | D00888 | 13 | | | D04968P | 5 | | | 278 |
| 857 | 24 | PK | | | 7-0 | 30-21-11 | D00888 | 9 | | | TB0070Y | A018 | BJ | | 050-099 |
| 857 | 24 | PK | | | 8-0 | 30-21-11 | D00888 | 9 | | | TB0070Y | A018 | BJ | | 150-199 |
| 858 | 22 | PA | | | 4-0 | 29-33-11 | TB0100Y | C025 | BJ | | D05732J | 14 | | | 050-099 |
| 858 | 22 | PA | | | 4-0 | 29-33-11 | D05732J | 14 | | | TB0100Y | C025 | BJ | | 150-199, 275-277, 280-299 |
| 858 | 22 | PA | | | 4-2 | 29-33-11 | D05732J | 14 | | | TB0100Y | C025 | BJ | | 278 |
| 863 | 22 | PA | | | 7-0 | 30-21-11 | D04968P | 17 | | | D00888 | 15 | | | 050-099 |
| 863 | 22 | PA | | | 8-0 | 30-21-11 | D04968P | 17 | | | D00888 | 15 | | | 150-154 |
| 863 | 22 | PA | | | 6-0 | 30-21-11 | D04968P | 17 | | | D00888 | 15 | | | 155-199 |
| 870 | 24 | PK | | | 7-0 | 30-21-11 | D04968P | 18 | | | TB0070Y | A018 | BJ | | 050-099, 155-199 |
| 870 | 24 | PK | | | 8-0 | 30-21-11 | D04968P | 18 | | | TB0070Y | A018 | BJ | | 150-154 |
| 871 | 22 | PA | | | 6-0 | 30-21-11 | D00888 | 7 | | | D04968P | 7 | | | 050-099, 155-199 |
| 871 | 22 | PA | | | 7-0 | 30-21-11 | D00888 | 7 | | | D04968P | 7 | | | 150-154 |
| 872 | 22 | PA | | | 6-0 | 30-21-11 | D00888 | 10 | | | D04968P | 20 | | | 050-099, 155-199 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 66

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 872 | 22 | | PA | 7-0 | 30-21-11 | D00888 | | 10 | | | | | D04968P | 20 | | | 150-154 |
| 873 | 22 | | PA | 7-0 | 33-16-26 | D10732 | | 3 | | | | | TB0098Y | C035 | BJ | | ALL |
| 874 | 22 | | PA | 7-0 | 33-16-26 | D10732 | | 4 | | | | | TB0098Z | 38 | BJ | | ALL |
| 876 | 22 | | PA | 14-0 | 29-21-32 | D10732 | | 6 | | | | | TB0070Y | A015 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 876 | 22 | | PA | 14-2 | 29-21-32 | D10732 | | 6 | | | | | TB0070Y | A015 | BJ | | 278 |
| 877 | 22 | | PA | 7-0 | 29-21-32 | D10732 | | 7 | | | | | TB0100Y | C031 | BJ | | ALL |
| 878 | 20 | | PA | 8-0 | 29-21-32 | D10732 | | 8 | | | | | GD04428 | D.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 878 | 20 | | PA | 7-4 | 29-21-32 | D10732 | | 8 | | | | | GD04428 | D.. | 2 | | 278 |
| 879 | 22 | | PA | 6-0 | 29-21-32 | D10732 | | 9 | | | | | D05732J | 5 | | | 050-099, 150-199, 275-277, 280-299 |
| 879 | 22 | | PA | 4-9 | 29-21-32 | D10732 | | 9 | | | | | D05732J | 5 | | | 278 |
| 880 | 22 | | PA | 6-0 | 29-21-32 | D10732 | | 10 | | | | | D05732J | 15 | | | 050-099, 150-199, 275-277, 280-299 |
| 880 | 22 | | PA | 4-9 | 29-21-32 | D10732 | | 10 | | | | | D05732J | 15 | | | 278 |
| 881 | 22 | | PA | 7-0 | 29-21-32 | D10732 | | 11 | | | | | TB0100Y | A030 | BJ | | ALL |
| 882 | 20 | | PA | 8-0 | 29-21-32 | D10732 | | 13 | | | | | GD04428 | A.. | 2 | | 050-099, 150-199, 275-277, 280-299 |
| 882 | 20 | | PA | 7-4 | 29-21-32 | D10732 | | 13 | | | | | GD04428 | A.. | 2 | | 278 |
| 883 | 22 | | PA | 4-0 | 29-21-32 | D04708J | | 40 | | | | | TB0098Y | C011 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 883 | 22 | | PA | 4-4 | 29-21-32 | D04708J | | 40 | | | | | TB0098Y | C011 | BJ | | 278 |
| 885 | 22 | | PA | 7-0 | 29-21-32 | D10732 | | 15 | | | | | TB0102Y | A015 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 885 | 22 | | PA | 7-1 | 29-21-32 | D10732 | | 15 | | | | | TB0102Y | A015 | BJ | | 278 |
| 886 | 22 | | PQ | AA | 4-0 | 29-11-31 | D05000P | 12 | | | | | TB0070Y | A015 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 886 | 22 | | PQ | AA | 3-6 | 29-11-31 | D05000P | 12 | | | | | TB0070Y | A015 | BJ | | 278 |
| 886Z | | | AA | 0-0 | 29-11-31 | D05000P | | DED | | | | | TB0070Y | DED | | | ALL |
| 887 | 22 | | PQ | AB | 6-0 | 29-11-31 | TB0100Y | A031 | BJ | | | | D04778J | 39 | | | 050-099, 150-199, 275-277, 280-299 |
| 887 | 22 | | PQ | AB | 4-9 | 29-11-31 | TB0100Y | A031 | BJ | | | | D04778J | 39 | | | 278 |
| 887Z | | | AB | 0-0 | 29-11-31 | TB0100Y | | DED | | | | | D04778J | DED | | | ALL |
| 888 | 22 | | PA | 6-0 | 29-21-32 | D10732 | | 2 | | | | | D04708J | 39 | | | 050-099 |
| 888 | 22 | | PA | 7-0 | 29-21-32 | D10732 | | 2 | | | | | D04708J | 39 | | | 150-199, 275-277, 280-299 |
| 888 | 22 | | PA | 5-4 | 29-21-32 | D10732 | | 2 | | | | | D04708J | 39 | | | 278 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 67

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286T0062 | | | P5 & P61-L2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 889 | 22 | | PA | | 6-0 | 29-21-32 | D04990J | | 17 | | TB0100Y | A030 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 889 | 22 | | PA | | 4-7 | 29-21-32 | D04990J | | 17 | | TB0100Y | A030 | BJ | | 278 |
| 890 | 22 | | PA | | 12-0 | 30-21-11 | D04708J | | 46 | | TB0070Y | A017 | BJ | | 050-099, 155-199 |
| 890 | 22 | | PA | | 13-0 | 30-21-11 | D04708J | | 46 | | TB0070Y | A017 | BJ | | 150-154 |
| FRB | | | | | 0-0 | 23-41-11 | D04955J | | 21 | | D04955J | | | FB | ALL |
| FRC | | | | | 0-0 | 73-21-11 | D04710J | | | FC | D04710J | | 21 | | ALL |
| FRY | | | | | 0-0 | 23-51-41 | D00557 | | 5 | | D00557 | | | FY | 150-199, 275-299 |
| FRZ | | | | | 0-0 | 23-51-41 | D00551 | | | FZ | D00551 | | 11 | | 150-199, 275-299 |
| GRA | | | | | 0-0 | 78-34-11 | D04710J | | | GA | D04710J | | 25 | | ALL |
| GRE | | | | | 0-0 | 78-34-11 | D04718J | | | GE | D04718J | | 26 | | ALL |
| GRF | | | | | 0-0 | 78-34-21 | D04710J | | | GF | D04710J | | 46 | | ALL |
| W0065 | 286T0065 | | | FLIGHT RECORDER CONTROL PANEL-P61 | | | | | | | | | | | |
| 001 | 22 | | PA | | 6-0 | 31-31-11 | D00493 | | 13 | | D04707J | | 1 | | ALL |
| 002 | 22 | | PA | | 6-0 | 31-31-11 | D00493 | | 12 | | D04707J | | 2 | | ALL |
| 005 | 24 | | PK | | 6-0 | 31-31-11 | D00493 | | 9 | | D04707J | | 5 | | ALL |
| 006 | 24 | | PK | | 7-0 | 31-31-11 | D00493 | | 6 | | D04707J | | 6 | | 050-099 |
| 006 | 24 | | PK | | 6-0 | 31-31-11 | D00493 | | 6 | | D04707J | | 6 | | 150-199, 275-299 |
| 007 | 20 | | PA | | 6-0 | 31-31-11 | D01445 | | 10 | | GD04432 | A.. | 2 | | ALL |
| 010 | 22 | | PA | | 3-0 | 31-31-11 | D01445 | | 11 | | D04707J | | 22 | | ALL |
| 011 | 22 | | PA | | 5-0 | 31-31-11 | D01445 | | 2 | | D00493 | | 8 | | ALL |
| 012 | 22 | | PA | | 5-0 | 31-31-11 | D01445 | | 1 | | D00493 | | 5 | | ALL |
| 013 | 20 | | PA | | 6-0 | 31-31-11 | D00493 | | 7 | | GD04432 | S.. | 2 | | ALL |
| 015 | 20 | | PA | | 6-0 | 31-31-11 | D00493 | | 14 | | GD04432 | D.. | 2 | | ALL |
| 018 | 24 | | PK | | 6-0 | 31-31-11 | D00493 | | 15 | | D04707J | | 25 | | ALL |
| 023 | 22 | | PQ | AW | 6-0 | 33-16-26 | D00493 | | 3 | | TB0098Z | | 37 | BJ | ALL |
| 023Z | | | | AW | 0-0 | 33-16-26 | D00493 | | DED | | TB0098Z | | DED | | ALL |
| 024 | 22 | | PQ | AX | 6-0 | 33-16-26 | D00493 | | 4 | | TB0098Z | | 38 | BJ | ALL |
| 024Z | | | | AX | 0-0 | 33-16-26 | D00493 | | DED | | TB0098Z | | DED | | ALL |
| 059 | 24 | | PK | | 6-0 | 31-31-22 | TB0106Y | | A029 | BJ | D04707J | | 49 | | 050-099 |
| 059 | 24 | | PK | | 7-0 | 31-31-22 | TB0106Y | | A029 | BJ | D04707J | | 49 | | 150-199, 275-299 |
| 060 | 24 | | PK | | 6-0 | 31-31-22 | TB0106Y | | C029 | BJ | D04707J | | 55 | | 050-099 |
| 060 | 24 | | PK | | 7-0 | 31-31-22 | TB0106Y | | C029 | BJ | D04707J | | 55 | | 150-199, 275-299 |
| 061 | 24 | | PK | | 6-0 | 23-22-15 | D02579 | | 17 | | TB0098X | | D022 | BJ | 050-099, 155-199, 275-299 |
| 061 | 24 | | PK | | 7-0 | 23-22-15 | D02579 | | 17 | | TB0098X | | D022 | BJ | 150-154 |
| 062 | 24 | | PK | | 6-0 | 31-35-11 | D02579 | | 16 | | D04707J | | 28 | | 050-099 |
| 065 | 24 | | PK | | 7-0 | 31-35-11 | D02579 | | 16 | | D04707J | | 28 | | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 68

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0065 | 286T0065 | | | FLIGHT RECORDER CONTROL PANEL-P61 (continued) | | | | | | | | | | | | | |
| 065 | 24 | | PK | 6-0 | 31-35-11 | D02579 | | 16 | | | | | D04707J | 28 | | | 155-199, 275-299 |
| 098 | 24 | | PK | 6-0 | 34-61-15 | D02581 | | 7 | | | | | D06225J | 10 | | | 050-099, 155-199, 275-299 |
| 098 | 24 | | PK | 7-0 | 34-61-15 | D02581 | | 7 | | | | | D06225J | 10 | | | 150-154 |
| 099 | 24 | | PK | 6-0 | 34-61-15 | D02581 | | 9 | | | | | D06225J | 11 | | | 050-099, 155-199, 275-299 |
| 099 | 24 | | PK | 7-0 | 34-61-15 | D02581 | | 9 | | | | | D06225J | 11 | | | 150-154 |
| 101 | 22 | | PA | 5-0 | 34-61-15 | D02583 | | 18 | | | | | D02577 | 18 | | | 050-099, 150-154 |
| 101 | 22 | | PA | 4-0 | 34-61-15 | D02583 | | 18 | | | | | D02577 | 18 | | | 155-199, 275-299 |
| 102 | 22 | | PA | 5-0 | 34-61-15 | D02583 | | 19 | | | | | D02577 | 19 | | | 050-099, 150-154 |
| 102 | 22 | | PA | 4-0 | 34-61-15 | D02583 | | 19 | | | | | D02577 | 19 | | | 155-199, 275-299 |
| 104 | 22 | | PA | 5-0 | 34-61-15 | D02583 | | 20 | | | | | D02577 | 20 | | | 050-099, 150-154 |
| 104 | 22 | | PA | 4-0 | 34-61-15 | D02583 | | 20 | | | | | D02577 | 20 | | | 155-199, 275-299 |
| 105 | 22 | | PA | 5-0 | 34-61-15 | D02583 | | 21 | | | | | D02577 | 21 | | | 050-099, 150-154 |
| 105 | 22 | | PA | 4-0 | 34-61-15 | D02583 | | 21 | | | | | D02577 | 21 | | | 155-199, 275-299 |
| 106 | 22 | | PA | 5-0 | 34-61-15 | D02583 | | 22 | | | | | D02577 | 22 | | | 050-099, 150-154 |
| 106 | 22 | | PA | 4-0 | 34-61-15 | D02583 | | 22 | | | | | D02577 | 22 | | | 155-199, 275-299 |
| 107 | 24 | | PK | 5-0 | 34-61-15 | D02583 | | 50 | | | | | D02577 | 50 | | | 050-099, 150-154 |
| 107 | 24 | | PK | 4-0 | 34-61-15 | D02583 | | 50 | | | | | D02577 | 50 | | | 155-199, 275-299 |
| 108 | 24 | | PK | 5-0 | 34-61-15 | D02583 | | 51 | | | | | D02577 | 51 | | | 050-099, 150-154 |
| 108 | 24 | | PK | 4-0 | 34-61-15 | D02583 | | 51 | | | | | D02577 | 51 | | | 155-199, 275-299 |
| 109 | 24 | | PK | 5-0 | 34-61-15 | D02583 | | 52 | | | | | D02577 | 52 | | | 050-099, 150-154 |
| 109 | 24 | | PK | 4-0 | 34-61-15 | D02583 | | 52 | | | | | D02577 | 52 | | | 155-199, 275-299 |
| 110 | 24 | | PK | 5-0 | 34-61-15 | D02583 | | 53 | | | | | D02577 | 53 | | | 050-099, 150-154 |
| 110 | 24 | | PK | 4-0 | 34-61-15 | D02583 | | 53 | | | | | D02577 | 53 | | | 155-199, 275-299 |
| 111 | 24 | | PK | 6-0 | 34-61-15 | D02579 | | 6 | | | | | D06225J | 2 | | | 050-099, 155-199, 275-299 |
| 111 | 24 | | PK | 7-0 | 34-61-15 | D02579 | | 6 | | | | | D06225J | 2 | | | 150-154 |
| 112 | 24 | | PK | 6-0 | 34-61-15 | D02579 | | 7 | | | | | D06225J | 3 | | | 050-099, 155-199, 275-299 |
| 112 | 24 | | PK | 7-0 | 34-61-15 | D02579 | | 7 | | | | | D06225J | 3 | | | 150-154 |
| 113 | 22 | | PA | 6-0 | 34-61-15 | D02579 | | 11 | | | | | TB0104X | C026 | BJ | | 050-099, 155-199, 275-299 |
| 113 | 22 | | PA | 7-0 | 34-61-15 | D02579 | | 11 | | | | | TB0104X | C026 | BJ | | 150, 153-154 |
| 113 | 20 | | PA | 7-0 | 34-61-15 | D02579 | | 11 | | | | | TB0104X | C026 | BJ | | 151-152 |
| 114 | 20 | | PA | 6-0 | 34-61-15 | D02579 | | 12 | | | | | GD04432 | A.. | 2 | | 050-099 |
| 114 | 20 | | PA | 8-0 | 34-61-15 | D02579 | | 12 | | | | | GD04432 | A.. | 2 | | 150-154 |
| 114 | 20 | | PA | 7-0 | 34-61-15 | D02579 | | 12 | | | | | GD04432 | A.. | 2 | | 155-199, 275-299 |
| 115 | 20 | | PA | 6-0 | 34-61-15 | D02581 | | 2 | | | | | GD04432 | S.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 69

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0065 | 286T0065 | | | FLIGHT RECORDER CONTROL PANEL-P61 (continued) | | | | | | | | | | | |
| 115 | 20 | | PA | | 8-0 | 34-61-15 | D02581 | | | | GD04432 | S.. | 2 | | 150-154 |
| 115 | 20 | | PA | | 7-0 | 34-61-15 | D02581 | | | | GD04432 | S.. | 2 | | 155-199, 275-299 |
| 116 | 24 | | PK | | 6-0 | 34-61-24 | D04707J | | | | TB0104X | D026 | BJ | | 050-099, 155-199, 276-299 |
| 201B | 24 | | PW | IA | 3-0 | 31-31-11 | D01445 | | | 5 | D04707J | | 15 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 31-31-11 | D01445 | | | 4 | D04707J | | 14 | | ALL |
| 201Z | | | | IA | 0-0 | 31-31-11 | D01445 | | | DED | D04707J | | 13 | | ALL |
| 202B | 24 | | PW | IB | 3-0 | 31-31-11 | D01445 | | | 7 | D04707J | | 17 | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 31-31-11 | D01445 | | | 6 | D04707J | | 16 | | ALL |
| 202Z | | | | IB | 0-0 | 31-31-11 | D01445 | | | DED | D04707J | | 18 | | ALL |
| 203B | 24 | | PW | IC | 3-0 | 31-31-11 | D01445 | | | 13 | D04707J | | 11 | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 31-31-11 | D01445 | | | 12 | D04707J | | 10 | | ALL |
| 203Z | | | | IC | 0-0 | 31-31-11 | D01445 | | | DED | D04707J | | 7 | | ALL |
| 214B | 24 | | PW | IN | 3-0 | 31-31-11 | D01445 | | | 9 | D04707J | | 36 | | ALL |
| 214R | 24 | | PW | IN | 0-0 | 31-31-11 | D01445 | | | 8 | D04707J | | 35 | | ALL |
| 214Z | | | | IN | 0-0 | 31-31-11 | D01445 | | | DED | D04707J | | 19 | | ALL |
| 226 | 20 | | UA | | 5-0 | 23-22-15 | TB0098X | | | REF | GD04432 | S.. | 2 | | 050-099 |
| 226 | 20 | | PA | | 5-0 | 23-22-15 | TB0098X | | | | GD04432 | S.. | 2 | | 150-154 |
| 226 | 20 | | PA | | 4-0 | 23-22-15 | TB0098X | | | | GD04432 | S.. | 2 | | 155-199 |
| 226 | 20 | | PA | | 4-0 | 23-22-15 | TB0098X | | | REF | GD04432 | S.. | 2 | | 275-299 |
| 226B | 24 | | PW | JA | 5-0 | 23-22-15 | D02579 | | | 15 | TB0098X | B022 | BJ | | 050-099 |
| 226B | 24 | | PW | JA | 7-0 | 23-22-15 | D02579 | | | 15 | TB0098X | B022 | BJ | | 150-154 |
| 226B | 24 | | PW | JA | 6-0 | 23-22-15 | D02579 | | | 15 | TB0098X | B022 | BJ | | 155-199, 275-299 |
| 226R | 24 | | PW | JA | 0-0 | 23-22-15 | D02579 | | | 13 | TB0098X | A022 | BJ | | ALL |
| 226Z | | | | JA | 0-0 | 23-22-15 | D02579 | | | DED | TB0098X | REF | | JA | 050-099, 275-299 |
| 226Z | | | | JA | 0-0 | 23-22-15 | D02579 | | | DED | TB0098X | | | JA | 150-199 |
| 227B | 24 | | PW | JB | 6-0 | 31-35-11 | D02579 | | | 14 | D04707J | | 52 | | 050-099, 155-199, 275-299 |
| 227B | 24 | | PW | JB | 7-0 | 31-35-11 | D02579 | | | 14 | D04707J | | 52 | | 150-154 |
| 227R | 24 | | PW | JB | 0-0 | 31-35-11 | D02579 | | | 3 | D04707J | | 51 | | ALL |
| 227Z | | | | JB | 0-0 | 31-35-11 | D02579 | | | DED | D04707J | | 50 | | ALL |
| 228B | 24 | | PW | JC | 5-0 | 34-61-15 | D02583 | | | 9 | D02577 | | 9 | | 050-099, 150-154 |
| 228B | 24 | | PW | JC | 4-0 | 34-61-15 | D02583 | | | 9 | D02577 | | 9 | | 155-199, 275-299 |
| 228R | 24 | | PW | JC | 0-0 | 34-61-15 | D02583 | | | 8 | D02577 | | 8 | | ALL |
| 228Z | | | | JC | 0-0 | 34-61-15 | D02583 | | | REF | D02577 | REF | | JE | 050-099, 275-299 |
| 228Z | | | | JC | 0-0 | 34-61-15 | D02583 | | | | D02577 | | | JE | 150-199 |
| 229B | 24 | | PW | JD | 5-0 | 34-61-15 | D02583 | | | 11 | D02577 | | 11 | | 050-099, 150-154 |
| 229B | 24 | | PW | JD | 4-0 | 34-61-15 | D02583 | | | 11 | D02577 | | 11 | | 155-199, 275-299 |
| 229R | 24 | | PW | JD | 0-0 | 34-61-15 | D02583 | | | 10 | D02577 | | 10 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 70

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|---------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0065 | 286T0065 | | | FLIGHT RECORDER CONTROL PANEL-P61 (continued) | | | | | | | | | | | | |
| 229Z | | | JD | 0-0 | 34-61-15 | D02583 | | REF | | JF | D02577 | REF | JE | 050-099, 275-299 | | |
| 229Z | | | JD | 0-0 | 34-61-15 | D02583 | | | | JF | D02577 | | JE | 150-199 | | |
| 230B | 24 | PW | JE | 5-0 | 34-61-15 | D02583 | | 13 | | | D02577 | 13 | | 050-099, 150-154 | | |
| 230B | 24 | PW | JE | 4-0 | 34-61-15 | D02583 | | 13 | | | D02577 | 13 | | 155-199, 275-299 | | |
| 230R | 24 | PW | JE | 0-0 | 34-61-15 | D02583 | | 12 | | | D02577 | 12 | | ALL | | |
| 230Z | | | JE | 0-0 | 34-61-15 | D02583 | | REF | | JF | D02577 | REF | JE | 050-099, 275-299 | | |
| 230Z | | | JE | 0-0 | 34-61-15 | D02583 | | | | JF | D02577 | | JE | 150-199 | | |
| 231B | 24 | PW | JF | 5-0 | 34-61-15 | D02583 | | 15 | | | D02577 | 15 | | 050-099, 150-154 | | |
| 231B | 24 | PW | JF | 4-0 | 34-61-15 | D02583 | | 15 | | | D02577 | 15 | | 155-199, 275-299 | | |
| 231R | 24 | PW | JF | 0-0 | 34-61-15 | D02583 | | 14 | | | D02577 | 14 | | ALL | | |
| 231Z | | | JF | 0-0 | 34-61-15 | D02583 | | REF | | JF | D02577 | REF | JE | 050-099, 275-299 | | |
| 231Z | | | JF | 0-0 | 34-61-15 | D02583 | | | | JF | D02577 | | JE | 150-199 | | |
| 232B | 24 | PW | JG | 5-0 | 34-61-15 | D02583 | | 2 | | | D02577 | 2 | | 050-099, 150-154 | | |
| 232B | 24 | PW | JG | 4-0 | 34-61-15 | D02583 | | 2 | | | D02577 | 2 | | 155-199, 275-299 | | |
| 232R | 24 | PW | JG | 0-0 | 34-61-15 | D02583 | | 1 | | | D02577 | 1 | | ALL | | |
| 232Z | | | JG | 0-0 | 34-61-15 | D02583 | | REF | | JH | D02577 | REF | JG | 050-099, 275-299 | | |
| 232Z | | | JG | 0-0 | 34-61-15 | D02583 | | | | JH | D02577 | | JG | 150-199 | | |
| 233B | 24 | PW | JH | 5-0 | 34-61-15 | D02583 | | 4 | | | D02577 | 4 | | 050-099, 150-154 | | |
| 233B | 24 | PW | JH | 4-0 | 34-61-15 | D02583 | | 4 | | | D02577 | 4 | | 155-199, 275-299 | | |
| 233R | 24 | PW | JH | 0-0 | 34-61-15 | D02583 | | 3 | | | D02577 | 3 | | ALL | | |
| 233Z | | | JH | 0-0 | 34-61-15 | D02583 | | REF | | JH | D02577 | REF | JG | 050-099, 275-299 | | |
| 233Z | | | JH | 0-0 | 34-61-15 | D02583 | | | | JH | D02577 | | JG | 150-199 | | |
| 234B | 24 | PW | JI | 6-0 | 34-61-15 | D02579 | | 5 | | | D06225J | 5 | | 050-099, 155-199, 275-299 | | |
| 234B | 24 | PW | JI | 7-0 | 34-61-15 | D02579 | | 5 | | | D06225J | 5 | | 150-154 | | |
| 234R | 24 | PW | JI | 0-0 | 34-61-15 | D02579 | | 4 | | | D06225J | 4 | | ALL | | |
| 234Z | | | JI | 0-0 | 34-61-15 | D02579 | | DED | | | D06225J | 6 | | ALL | | |
| 235B | 24 | PW | JJ | 6-0 | 34-61-15 | D02579 | | 9 | | | D06225J | 8 | | 050-099, 155-199, 275-299 | | |
| 235B | 24 | PW | JJ | 7-0 | 34-61-15 | D02579 | | 9 | | | D06225J | 8 | | 150-154 | | |
| 235R | 24 | PW | JJ | 0-0 | 34-61-15 | D02579 | | 10 | | | D06225J | 7 | | ALL | | |
| 235Z | | | JJ | 0-0 | 34-61-15 | D02579 | | DED | | | D06225J | 9 | | ALL | | |
| 237B | 24 | PW | JL | 6-0 | 34-61-15 | D02581 | | 5 | | | D06225J | 13 | | 050-099, 155-199, 275-299 | | |
| 237B | 24 | PW | JL | 7-0 | 34-61-15 | D02581 | | 5 | | | D06225J | 13 | | 150-154 | | |
| 237R | 24 | PW | JL | 0-0 | 34-61-15 | D02581 | | 3 | | | D06225J | 12 | | ALL | | |
| 237Z | | | JL | 0-0 | 34-61-15 | D02581 | | DED | | | D06225J | 14 | | ALL | | |
| 301B | 24 | PX | MA | 5-0 | 31-31-19 | D04707J | | 38 | | | TB0098Y | C015 | BJ | 050-099 | | |
| 301B | 24 | PX | MA | 6-0 | 31-31-19 | TB0098Y | | C015 | BJ | | D04707J | 38 | | 150-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 71

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0065 | 286T0065 | | | FLIGHT RECORDER CONTROL PANEL-P61 (continued) | | | | | | | | | | | |
| 301R | 24 | PX | MA | | 0-0 | 31-31-19 | D04707J | | 37 | | TB0098Y | A015 | BJ | | 050-099 |
| 301R | 24 | PX | MA | | 0-0 | 31-31-19 | TB0098Y | A015 | BJ | | D04707J | | 37 | | 150-199, 275-299 |
| 301Y | 24 | PX | MA | | 0-0 | 31-31-19 | D04707J | | 39 | | TB0098Y | A016 | BJ | | 050-099 |
| 301Y | 24 | PX | MA | | 0-0 | 31-31-19 | TB0098Y | A016 | BJ | | D04707J | | 39 | | 150-199, 275-299 |
| 301Z | | | MA | | 0-0 | 31-31-19 | D04707J | | 40 | | TB0098Y | DED | | | 050-099 |
| 301Z | | | MA | | 0-0 | 31-31-19 | TB0098Y | | DED | | D04707J | | 40 | | 150-199, 275-299 |
| 901 | 20 | PA | | | 10-0 | 23-25-13 | D06225J | | | IJ | GD04432 | S.. | E | | 150, 153-199 |
| 901B | 22 | PR | IJ | | 10-0 | 23-25-13 | D02581 | | 6 | | D06225J | | 17 | | 150, 153-199 |
| 901R | 22 | PR | IJ | | 0-0 | 23-25-13 | D02581 | | 4 | | D06225J | | 16 | | 150, 153-199 |
| 901Z | | | IJ | | 0-0 | 23-25-13 | D02581 | DED | | | D06225J | | | IJ | 150, 153-199 |
| 903 | 22 | PA | | | 10-0 | 23-25-13 | D02581 | | 8 | | D06225J | | 19 | | 150, 153-199 |
| FRE | | | | | 0-0 | 34-61-15 | D02577 | REF | | JE | D02577 | | 16 | | 050-099 |
| FRE | | | | | 0-0 | 34-61-15 | D02577 | | 16 | | D02577 | | | JE | 150-199 |
| FRE | | | | | 0-0 | 34-61-15 | D02577 | | 16 | | D02577 | REF | | JE | 275-299 |
| FRF | | | | | 0-0 | 34-61-15 | D02583 | | 16 | | D02583 | REF | | JF | 050-099, 275-299 |
| FRF | | | | | 0-0 | 34-61-15 | D02583 | | 16 | | D02583 | | | JF | 150-199 |
| FRG | | | | | 0-0 | 34-61-15 | D02577 | REF | | JG | D02577 | | 5 | | 050-099 |
| FRG | | | | | 0-0 | 34-61-15 | D02577 | | 5 | | D02577 | | | JG | 150-199 |
| FRG | | | | | 0-0 | 34-61-15 | D02577 | | 5 | | D02577 | REF | | JG | 275-299 |
| FRH | | | | | 0-0 | 34-61-15 | D02583 | | 5 | | D02583 | REF | | JH | 050-099, 275-299 |
| FRH | | | | | 0-0 | 34-61-15 | D02583 | | 5 | | D02583 | | | JH | 150-199 |
| FRJ | | | | | 0-0 | 23-25-13 | D06225J | | 18 | | D06225J | | | IJ | 150, 153-199 |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL | | | | | | | | | | | |
| 001 | 24 | PK | | | 15-0 | 24-51-71 | D01360 | | 1 | | TB0102Y | C016 | BJ | | ALL |
| 002 | 24 | PK | | | 15-0 | 24-51-71 | D01360 | | 2 | | TB0100Y | C016 | BJ | | ALL |
| 003 | 22 | PA | | | 8-0 | 33-16-17 | TB0066Z | | 27 | BJ | D01360 | | 3 | | ALL |
| 004 | 22 | PA | | | 8-0 | 33-16-17 | TB0066Z | | 29 | BJ | D01360 | | 4 | | ALL |
| 006 | 22 | PQ | TQ | | 15-0 | 29-32-11 | D01360 | | 6 | | TB0102Y | A029 | BJ | | ALL |
| 006Z | | | TQ | | 0-0 | 29-32-11 | D01360 | DED | | | TB0102Y | DED | | | ALL |
| 008 | 24 | PK | | | 8-0 | 29-11-12 | D05006P | | 11 | | D01360 | | 8 | | ALL |
| 009 | 22 | PA | | | 15-0 | 29-11-12 | D05406J | | 6 | | D01360 | | 9 | | 050-099 |
| 009 | 22 | PA | | | 16-0 | 29-11-12 | D01360 | | 9 | | D05406J | | 6 | | 150-199, 275-299 |
| 010 | 22 | PA | | | 15-0 | 29-11-12 | D04650J | | 52 | | D01360 | | 10 | | ALL |
| 011 | 22 | PA | | | 15-0 | 29-11-12 | D04650J | | 53 | | D01360 | | 11 | | ALL |
| 012 | 24 | PK | | | 15-0 | 29-11-12 | D04650J | | 58 | | D01360 | | 12 | | ALL |
| 014 | 24 | PK | | | 15-0 | 29-11-12 | D04650J | | 51 | | D01360 | | 14 | | ALL |
| 015 | 22 | PQ | TR | | 15-0 | 29-32-11 | D01360 | | 15 | | TB0102Y | C029 | BJ | | ALL |
| 015Z | | | TR | | 0-0 | 29-32-11 | D01360 | DED | | | TB0102Y | DED | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0060
Page 72
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 016 | 24 | PV | AP | 8-0 | 29-11-31 | D01360 | | 16 | | | | | D05006P | 12 | | | ALL |
| 016Z | | | AP | 0-0 | 29-11-31 | D01360 | | DED | | | | | D05006P | DED | | | ALL |
| 017 | 24 | PV | AQ | 15-0 | 29-11-31 | D01360 | | 17 | | | | | TB0102X | D005 | BJ | | ALL |
| 017Z | | | AQ | 0-0 | 29-11-31 | D01360 | | DED | | | | | TB0102X | DED | | | ALL |
| 018 | 22 | PA | | 15-0 | 29-11-31 | D01360 | | 18 | | | | | TB0102Y | C030 | BJ | | ALL |
| 01A | 20 | PA | | 7-0 | 33-13-16 | D03842 | | 1 | | | | | TB0068G | 5 | 2 | | ALL |
| 01B | 20 | PA | | 6-0 | 33-13-16 | D03842 | | 2 | | | | | GD00112 | A.. | 2 | | ALL |
| 01C | 22 | PQ | SC | 7-0 | 33-16-17 | TB0066Y | | A035 | BJ | | | | D03842 | 3 | | | ALL |
| 01CZ | | | SC | 0-0 | 33-16-17 | TB0066Y | | DED | | | | | D03842 | DED | | | ALL |
| 01D | 22 | PA | | 7-0 | 33-16-17 | TB0066Z | | 28 | BJ | | | | D03842 | 4 | | | ALL |
| 01E | 24 | PK | | 14-0 | 21-43-11 | D05006P | | 3 | | | | | D05062J | 7 | | | 050-099, 150-199 |
| 01E | 22 | PA | | 14-0 | 21-43-11 | D05006P | | 3 | | | | | D05062J | 7 | | | 275-299 |
| 01F | 22 | PA | | 14-0 | 21-44-11 | D03842 | | 6 | | | | | D05062J | 11 | | | ALL |
| 01G | 22 | PA | | 14-0 | 21-44-21 | D03842 | | 7 | | | | | D04870J | 28 | | | ALL |
| 01H | 20 | PA | | 7-0 | 21-43-11 | D03842 | | 8 | | | | | GD00112 | D.. | 2 | | 050-099, 150-199 |
| 01H | 24 | PK | | 7-0 | 21-43-11 | D03842 | | 8 | | | | | GD00112 | D.. | 2 | | 275-278 |
| 01H | 20 | PA | | 6-0 | 21-43-11 | D03842 | | 8 | | | | | GD00112 | D.. | 2 | | 280-299 |
| 01K | 24 | PK | | 14-0 | 21-43-11 | D03842 | | 10 | | | | | TB0104X | B003 | BJ | | ALL |
| 01N | 24 | PK | | 14-0 | 21-43-11 | D03842 | | 5 | | | | | TB0102Y | C033 | BJ | | ALL |
| 01P | 24 | PK | | 7-0 | 21-44-11 | D03842 | | 14 | | | | | D05006P | 5 | | | ALL |
| 01R | 24 | PK | | 14-0 | 21-44-11 | D03842 | | 15 | | | | | D05062J | 13 | | | ALL |
| 01S | 24 | PK | | 14-0 | 21-44-11 | D03842 | | 16 | | | | | D05062J | 16 | | | ALL |
| 01T | 24 | PK | | 7-0 | 21-44-11 | D03842 | | 17 | | | | | TB0066Y | A015 | BJ | | ALL |
| 01V | 24 | PK | | 14-0 | 21-44-11 | D03842 | | 19 | | | | | TB0102X | A002 | BJ | | ALL |
| 01W | 24 | PK | | 14-0 | 21-44-21 | D03842 | | 20 | | | | | D04870J | 27 | | | ALL |
| 01Y | 24 | PK | | 15-0 | 21-44-21 | D03842 | | 22 | | | | | D03846 | 6 | | | ALL |
| 01Z | 24 | PK | | 7-0 | 21-44-21 | D05006P | | 7 | | | | | D03842 | 23 | | | ALL |
| 020 | 22 | PA | | 15-0 | 29-11-12 | D04650J | | 54 | | | | | D01360 | 20 | | | ALL |
| 022 | 24 | PK | | 15-0 | 24-51-71 | D01360 | | 22 | | | | | TB0102Y | C016 | BJ | | ALL |
| 023 | 24 | PK | | 15-0 | 24-51-71 | D01360 | | 23 | | | | | TB0100Y | C016 | BJ | | ALL |
| 024 | 22 | PA | | 15-0 | 29-33-11 | D01360 | | 24 | | | | | D04870J | 30 | | | ALL |
| 029 | 20 | PA | | 4-0 | 78-34-21 | D05006P | | 14 | | | | | GD00102 | D.. | 2 | | ALL |
| 02A | 24 | PK | | 14-0 | 21-44-21 | D03842 | | 24 | | | | | D05356J | 20 | | | ALL |
| 02B | 24 | PK | | 14-0 | 21-44-21 | D03842 | | 25 | | | | | D05356J | 22 | | | ALL |
| 02C | 24 | PK | | 7-0 | 21-26-21 | D03842 | | 26 | | | | | TB0066Y | C019 | BJ | | ALL |
| 02E | 24 | PK | | 14-0 | 21-26-21 | D03842 | | 28 | | | | | D04870J | 22 | | | ALL |
| 02F | 24 | PK | | 13-0 | 21-26-21 | D03842 | | 29 | | | | | D04870J | 23 | | | ALL |
| 02H | 24 | PK | | 16-0 | 21-26-21 | D03842 | | 31 | | | | | D03846 | 9 | | | ALL |
| 030 | 20 | PA | | 4-0 | 78-34-21 | D05006P | | 15 | | | | | GD00102 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 73

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286T0066 | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 036 | 22 | PQ | BK | | 15-0 | 29-11-12 | D04870J | | 3 | | D03902 | | 6 | | ALL |
| 036Z | | | BK | | 0-0 | 29-11-12 | D04870J | | DED | | D03902 | | DED | | ALL |
| 037 | 22 | PA | | | 15-0 | 29-32-11 | D03902 | | 7 | | D04650J | | 50 | | ALL |
| 038 | 22 | PA | | | 13-0 | 29-11-21 | D03902 | | 8 | | TB0104Y | C013 | BJ | | ALL |
| 039 | 22 | PA | | | 13-0 | 29-11-21 | D03902 | | 9 | | TB0104Y | A013 | BJ | | ALL |
| 03A | 20 | PA | | | 8-0 | 33-13-16 | D00854 | | 1 | | TB0064G | | 7 | 2 | ALL |
| 03B | 20 | PA | | | 7-0 | 33-13-16 | D00854 | | 2 | | GD00102 | A.. | 2 | | ALL |
| 03C | 22 | PQ | FC | | 8-0 | 33-16-17 | D03902 | | 11 | | TB0068G | | 8 | 2 | ALL |
| 03CZ | | | FC | | 0-0 | 33-16-17 | D03902 | | DED | | TB0068G | | DED | | ALL |
| 03D | 22 | PA | | | 8-0 | 33-16-17 | D03902 | | 12 | | TB0068Z | | 15 | BJ | ALL |
| 03E | 20 | PA | | | 7-0 | 33-24-11 | D00854 | | 5 | | GD00104 | D.. | 2 | | ALL |
| 03F | 24 | PK | | | 15-0 | 33-24-11 | D00854 | | 6 | | D04650J | | 57 | | ALL |
| 03G | 24 | PK | | | 15-0 | 33-24-11 | D00854 | | 7 | | D05124J | | 13 | | ALL |
| 03H | 20 | PA | | | 7-0 | 33-24-11 | D00854 | | 8 | | GD00104 | D.. | 2 | | ALL |
| 03K | 24 | PK | | | 15-0 | 33-24-11 | D00854 | | 10 | | D04650J | | 56 | | 050-099, 150-199 |
| 03K | 24 | PK | | | 14-0 | 33-24-11 | D00854 | | 10 | | D04650J | | 56 | | 275-299 |
| 03L | 24 | PK | | | 15-0 | 33-24-11 | D00854 | | 11 | | D05124J | | 11 | | ALL |
| 042 | 20 | PA | | | 7-0 | 21-61-11 | D00490 | | 12 | | GD00104 | S.. | 2 | | ALL |
| 044 | 24 | PK | | | 14-0 | 21-61-11 | D00490 | | 4 | | TB0102Y | A036 | BJ | | ALL |
| 045 | 22 | PA | | | 6-0 | 33-51-11 | D06442J | | 8 | | TB0104X | C007 | BJ | | ALL |
| 046 | 24 | PK | | | 15-0 | 21-61-11 | D00490 | | 6 | | D05724J | | 7 | | ALL |
| 048 | 24 | PK | | | 15-0 | 21-61-11 | D00490 | | 8 | | D05724J | | 6 | | ALL |
| 049 | 24 | PK | | | 15-0 | 21-61-11 | D00490 | | 9 | | D05724J | | 9 | | ALL |
| 04B | 20 | PA | | | 7-0 | 25-65-12 | D01164 | | 2 | | GD04438 | D.. | 2 | | ALL |
| 04C | 22 | PA | | | 6-0 | 25-65-12 | D01164 | | 3 | | TB0096G | | 17 | 2 | ALL |
| 04E | 22 | PA | | | 6-0 | 25-65-12 | D01164 | | 5 | | D05124J | | 33 | | ALL |
| 04F | 22 | PA | | | 6-0 | 25-65-11 | D01164 | | 6 | | D05124J | | 31 | | ALL |
| 04G | 22 | PA | | | 6-0 | 25-65-12 | D01164 | | 7 | | D05124J | | 35 | | ALL |
| 04K | 20 | PA | | | 7-0 | 25-65-12 | D01164 | | 10 | | GD04438 | D.. | 2 | | ALL |
| 04M | 22 | PA | | | 6-0 | 25-65-12 | D01164 | | 12 | | D05124J | | 32 | | ALL |
| 050 | 24 | PK | | | 15-0 | 21-61-11 | D00490 | | 10 | | D05724J | | 8 | | ALL |
| 052 | 20 | PA | | | 7-0 | 21-61-21 | D00492 | | 7 | | GD00104 | S.. | 2 | | 050-099 |
| 052 | 20 | PA | | | 8-0 | 21-61-21 | D00492 | | 7 | | GD00104 | S.. | 2 | | 150-199, 275-299 |
| 059 | 20 | PA | | | 7-0 | 21-61-21 | D00492 | | 10 | | GD00104 | D.. | 2 | | 050-099 |
| 059 | 20 | PA | | | 8-0 | 21-61-21 | D00492 | | 10 | | GD00104 | D.. | 2 | | 150-199, 275-299 |
| 05C | 22 | PQ | TX | | 7-0 | 33-16-17 | TB0070Z | | 33 | BJ | D02888 | | 3 | | 050-099 |
| 05C | 22 | PQ | TX | | 6-0 | 33-16-17 | TB0070Z | | 33 | BJ | D02888 | | 3 | | 150-199, 275-299 |
| 05CZ | | | TX | | 0-0 | 33-16-17 | TB0070Z | | DED | | D02888 | | DED | | ALL |
| 05D | 22 | PQ | TW | | 7-0 | 33-16-17 | TB0070Z | | 34 | BJ | D02888 | | 4 | | 050-099 |

WIRE LIST

D280T132

91-21-11
 Section W0060
 Page 74
 Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286T0066 | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 05D | 22 | PQ | TW | | 6-0 | 33-16-17 | TB0070Z | 34 | BJ | | D02888 | 4 | | | 150-199, 275-299 |
| 05DZ | | | TW | | 0-0 | 33-16-17 | TB0070Z | | DED | | D02888 | | DED | | ALL |
| 05E | 22 | PA | | | 14-0 | 30-31-11 | D02888 | 5 | | | D05906J | 20 | | | ALL |
| 05F | 22 | PA | | | 14-0 | 30-32-11 | D02888 | 6 | | | D05906J | 5 | | | ALL |
| 05G | 22 | PA | | | 14-0 | 30-31-13 | D02888 | 7 | | | D05656J | 34 | | | ALL |
| 05H | 22 | PA | | | 14-0 | 30-33-11 | D02888 | 8 | | | D05656J | 16 | | | ALL |
| 05S | 22 | PA | | | 6-0 | 29-11-31 | D04870J | 7 | | | TB0102Y | C030 | BJ | | ALL |
| 05T | 22 | PA | | | 6-0 | 29-11-31 | D05406J | 27 | | | TB0102Y | C030 | BJ | | ALL |
| 060 | 24 | PK | | | 15-0 | 21-61-21 | D00492 | 9 | | | D05724J | 17 | | | ALL |
| 062 | 20 | PA | | | 7-0 | 21-61-31 | D01068 | 12 | | | GD00104 | S.. | 2 | | ALL |
| 066 | 22 | PQ | FG | | 8-0 | 33-16-17 | D01348 | 41 | | | TB0068Y | C019 | BJ | | ALL |
| 066Z | | | FG | | 0-0 | 33-16-17 | D01348 | | DED | | TB0068Y | | DED | | ALL |
| 067 | 22 | PA | | | 8-0 | 33-16-17 | D01348 | 42 | | | TB0068Z | 22 | BJ | | ALL |
| 069 | 20 | PA | | | 7-0 | 21-61-31 | D01068 | 9 | | | GD00104 | D.. | 2 | | ALL |
| 06C | 24 | PK | | | 6-0 | 21-26-21 | D03846 | 3 | | | D04870J | 38 | | | ALL |
| 06E | 24 | PK | | | 6-0 | 21-26-21 | D03846 | 5 | | | D04870J | 37 | | | ALL |
| 06G | 24 | PK | | | 6-0 | 21-44-21 | D03846 | 7 | | | D04870J | 24 | | | ALL |
| 06H | 24 | PK | | | 6-0 | 21-44-21 | D03846 | 8 | | | D04870J | 25 | | | ALL |
| 06L | 24 | PK | | | 16-0 | 21-26-21 | D03846 | 11 | | | D05406J | 12 | | | 050-099 |
| 06L | 24 | PK | | | 7-0 | 21-26-21 | D03846 | 11 | | | D05406J | 12 | | | 150-199, 275-299 |
| 070 | 24 | PK | | | 15-0 | 21-61-31 | D01068 | 10 | | | D05724J | 30 | | | ALL |
| 071 | 18 | PA | | | 8-0 | 33-13-16 | D01348 | 1 | DK | | TB0068H | 1 | 2 | | ALL |
| 072 | 18 | PA | | | 7-0 | 33-13-16 | D01348 | 2 | DK | | GD00112 | A.. | 2 | | ALL |
| 073 | 22 | PA | | | 8-0 | 33-16-17 | TB0066Z | 27 | BJ | | D01348 | 3 | | | ALL |
| 074 | 22 | PA | | | 8-0 | 33-16-17 | TB0066Z | 29 | BJ | | D01348 | 4 | | | ALL |
| 076 | 24 | PK | | | 15-0 | 36-11-21 | D01348 | 6 | | | D04870J | 16 | | | ALL |
| 077 | 24 | PK | | | 14-0 | 36-11-21 | D01348 | 7 | | | D07974J | 1 | | | ALL |
| 078 | 24 | PK | | | 15-0 | 36-11-21 | D01348 | 8 | | | D04870J | 18 | | | ALL |
| 080 | 24 | PK | | | 14-0 | 36-11-41 | D01348 | 10 | | | D04870J | 46 | | | ALL |
| 081 | 24 | PK | | | 8-0 | 36-11-41 | D01348 | 11 | | | TB0064D | A010 | 2 | | ALL |
| 082 | 24 | PK | | | 15-0 | 36-11-52 | D01348 | 12 | | | D05764J | 4 | | | ALL |
| 083 | 24 | PK | | | 15-0 | 36-11-52 | D01348 | 13 | | | TB0104X | D004 | BJ | | ALL |
| 085 | 22 | PA | | | 15-0 | 36-22-11 | D01348 | 15 | | | D04766J | 55 | | | ALL |
| 086R | 22 | PH | | | 12-0 | 26-18-21 | D01348 | 16 | | | TB0100D | A010 | 2 | | 050-099 |
| 086R | 22 | PH | | | 13-0 | 26-18-21 | D01348 | 16 | | | TB0100Y | A011 | BJ | | 150-157, 275-299 |
| 086R | 22 | PH | | | 13-0 | 26-18-21 | D01348 | 16 | | | TB0100D | A010 | 2 | | 162-199 |
| 087 | 24 | PK | | | 15-0 | 36-11-41 | D01348 | 17 | | | D04870J | 14 | | | ALL |
| 088 | 24 | PK | | | 15-0 | 36-11-41 | D01348 | 18 | | | D04870J | 55 | | | ALL |
| 08G | 16 | PA | | | 6-0 | 33-11-14 | TB0096G | 21 | 2 | | D04994J | 20 | FM | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 75

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 08G | 16 | | PA | | 5-0 | 33-11-14 | TB0096G | 21 | 2 | | D04994J | 20 | FM | | 150-199, 275-299 |
| 096 | 24 | | PK | | 14-0 | 36-11-62 | D01348 | 26 | | | D05764J | 6 | | | ALL |
| 097 | 20 | | PA | | 7-0 | 36-11-62 | D01348 | 27 | | | GD00104 | D.. | 2 | | ALL |
| 09J | 20 | | PA | | 7-0 | 21-61-41 | D10706 | 10 | | | GD00104 | D.. | 2 | | 050-099, 275-299 |
| 09J | 20 | | PA | | 8-0 | 21-61-41 | D10706 | 10 | | | GD00104 | D.. | 2 | | 150-199 |
| 09K | 24 | | PK | | 15-0 | 21-61-41 | D10706 | 9 | | | D05724J | 44 | | | ALL |
| 09M | 20 | | PA | | 7-0 | 21-61-41 | D10706 | 7 | | | GD00104 | S.. | 2 | | 050-099, 275-299 |
| 09M | 20 | | PA | | 8-0 | 21-61-41 | D10706 | 7 | | | GD00104 | S.. | 2 | | 150-199 |
| 104 | 22 | | PA | | 15-0 | 36-11-21 | D01348 | 34 | | | D04870J | 20 | | | ALL |
| 106 | 22 | | PA | | 15-0 | 36-11-21 | D01348 | 36 | | | D04870J | 26 | | | ALL |
| 109 | 22 | | PA | | 15-0 | 36-11-41 | D01348 | 39 | | | D04870J | 19 | | | ALL |
| 10G | 20 | | PA | | 7-0 | 33-13-21 | D10398 | 7 | | | GD04442 | S.. | 2 | | 050-099 |
| 10G | 20 | | PA | | 6-0 | 33-13-21 | D10398 | 7 | | | GD04442 | S.. | 2 | | 150-199, 275-299 |
| 10H | 18 | | PA | | 7-0 | 33-13-21 | D10398 | 8 | DK | | TB0096G | 30 | 2 | | ALL |
| 10L | 16 | | PA | | 7-0 | 33-13-21 | D10398 | 11 | FM | | GD04442 | A.. | 2 | | 050-099 |
| 10L | 16 | | PA | | 6-0 | 33-13-21 | D10398 | 11 | FM | | GD04442 | A.. | 2 | | 150-199, 275-299 |
| 10M | 22 | | PA | | 7-0 | 33-13-21 | D10398 | 12 | | | D07988J | 1 | | | ALL |
| 115 | 24 | | PK | | 15-0 | 36-11-21 | D01348 | 35 | | | D05406J | 11 | | | ALL |
| 116 | 22 | | PA | | 15-0 | 36-11-52 | D01348 | 46 | | | D05764J | 3 | | | ALL |
| 118 | 22 | | PA | | 3-0 | 78-36-11 | D07986J | 5 | | | TB0102X | B010 | BJ | | 050-099, 275-299 |
| 118 | 22 | | PA | | 4-0 | 78-36-11 | D07986J | 5 | | | TB0102X | B010 | BJ | | 150-199 |
| 120 | 22 | | PA | | 5-0 | 78-36-21 | D07986J | 1 | | | D04760J | 9 | | | 050-099 |
| 120 | 22 | | PA | | 6-0 | 78-36-21 | D07986J | 1 | | | D04760J | 9 | | | 150-199, 275-299 |
| 125 | 22 | | PA | | 15-0 | 36-11-62 | D01348 | 55 | | | D05764J | 5 | | | ALL |
| 126 | 20 | | PA | | 8-0 | 33-13-16 | D02085 | 1 | | | TB0068H | 6 | 2 | | ALL |
| 127 | 20 | | PA | | 7-0 | 33-13-16 | D02085 | 2 | | | GD00102 | A.. | 2 | | ALL |
| 128 | 22 | | PA | | 8-0 | 33-16-17 | D02085 | 3 | | | TB0068G | 8 | 2 | | ALL |
| 129 | 22 | | PA | | 8-0 | 33-16-17 | D02085 | 4 | | | TB0068Z | 15 | BJ | | ALL |
| 130 | 18 | | PA | | 6-0 | 25-31-12 | D04794J | 45 | DK | | TB0102G | 41 | 2 | | 050-099 |
| 130 | 18 | | PA | | 7-0 | 25-31-12 | TB0102G | 41 | 2 | | D04794J | 45 | DK | | 150-199 |
| 131 | 20 | | PA | | 8-0 | 33-13-16 | D01366 | 1 | | | TB0064G | 4 | 2 | | ALL |
| 132 | 20 | | PA | | 7-0 | 33-13-16 | D01366 | 2 | | | GD00112 | A.. | 2 | | ALL |
| 133 | 22 | | PQ | SE | 8-0 | 33-16-17 | TB0066Y | C035 | BJ | | D01366 | 3 | | | ALL |
| 133Z | | | | SE | 0-0 | 33-16-17 | TB0066Y | DED | | | D01366 | DED | | | ALL |
| 134 | 22 | | PA | | 8-0 | 33-16-17 | TB0066Z | 28 | BJ | | D01366 | 4 | | | ALL |
| 135 | 20 | | PA | | 7-0 | 21-58-11 | D01366 | 5 | | | GD00104 | D.. | 2 | | ALL |
| 137 | 22 | | PA | | 12-0 | 21-58-11 | D01366 | 7 | | | TB0102Y | C015 | BJ | | 050-099 |
| 137 | 22 | | PA | | 13-0 | 21-58-11 | D01366 | 7 | | | TB0102Y | C015 | BJ | | 150-199, 275-299 |
| 138 | 24 | | PK | | 15-0 | 21-58-12 | D01366 | 8 | | | TB0106X | C010 | BJ | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 76
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 138 | 24 | | PK | 12-0 | 21-58-12 | D01366 | | | 8 | | | | TB0106X | C010 | BJ | | 150-199, 275-299 |
| 139 | 22 | | PA | 13-0 | 21-58-16 | D01366 | | | 9 | | | | TB0102Y | C037 | BJ | | 050-099 |
| 139 | 22 | | PA | 15-0 | 21-58-16 | D01366 | | | 9 | | | | TB0102Y | C037 | BJ | | 150-199, 275-299 |
| 142 | 24 | | PK | 15-0 | 21-58-16 | D01366 | | | 12 | | | | D04870J | 5 | | | ALL |
| 144 | 24 | | PK | 15-0 | 21-58-16 | D01366 | | | 14 | | | | D04870J | 34 | | | ALL |
| 145 | 24 | | PK | 15-0 | 21-58-14 | D01366 | | | 15 | | | | D05764J | 10 | | | ALL |
| 146 | 24 | | PK | 6-0 | 21-58-11 | D05416J | | | 18 | | | | TB0102Y | A030 | BJ | | ALL |
| 147 | 24 | | PK | 12-0 | 21-58-11 | D01366 | | | 10 | | | | TB0102Y | C015 | BJ | | 050-099 |
| 147 | 24 | | PK | 13-0 | 21-58-11 | D01366 | | | 10 | | | | TB0102Y | C015 | BJ | | 150-199, 275-299 |
| 149 | 24 | | PK | 13-0 | 21-58-11 | D01366 | | | 11 | | | | TB0102Y | C028 | BJ | | ALL |
| 15A | 24 | | PK | 5-0 | 73-21-15 | D04758J | | | 53 | | | | TB0100X | C008 | BJ | | ALL |
| 170 | 22 | | PA | 13-0 | 31-31-26 | D03902 | | | 10 | | | | TB0104X | B005 | BJ | | ALL |
| 172 | 22 | | PA | 5-0 | 21-26-31 | D07972J | | | 26 | | | | D04766J | 4 | | | 050-099 |
| 172 | 22 | | PA | 5-0 | 21-26-31 | D04766J | | | 4 | | | | D07972J | 26 | | | 150-199, 275-299 |
| 173 | 22 | | PA | 5-0 | 30-46-11 | D07972J | | | 25 | | | | D05124J | 17 | | | ALL |
| 175 | 20 | | PA | 7-0 | 33-13-16 | D13584 | | | 1 | | | | TB0064G | 8 | 2 | | 050-099, 275-299 |
| 175 | 20 | | UA | 7-0 | 33-13-16 | D13584 | | | 1 | | | | TB0064G | 8 | 2 | | 150-199 |
| 176 | 20 | | PA | 6-0 | 33-13-16 | D13584 | | | 2 | | | | GD00112 | A.. | 2 | | 050-099, 275-299 |
| 176 | 20 | | UA | 6-0 | 33-13-16 | D13584 | | | 2 | | | | GD00112 | A.. | 2 | | 150-199 |
| 177 | 22 | | PQ | 5-0 | 21-28-11 | D04766J | | | 5 | | | | TB0104X | D008 | BJ | | 050-099 |
| 177 | 22 | | PA | 5-0 | 21-28-11 | D04766J | | | 5 | | | | TB0104X | D008 | BJ | | 150-199, 275-299 |
| 177Z | | | | 0-0 | 21-28-11 | D04766J | | | | | | | TB0104X | DED | | | 050-099 |
| 179 | 24 | | PK | 6-0 | 21-61-81 | TB0100Y | | | | | | | D05724J | 20 | | | 050-099 |
| 179 | 24 | | PK | 6-0 | 21-61-81 | D05724J | | | | | | | TB0100Y | C015 | BJ | | 150-199, 275-299 |
| 182 | 22 | | PA | 7-0 | 33-16-17 | D13584 | | | 3 | | | | TB0070Z | 29 | BJ | | 050-099 |
| 182 | 22 | | PA | 6-0 | 33-16-17 | D13584 | | | 3 | | | | TB0070Z | 29 | BJ | | 150-199, 275-299 |
| 183 | 22 | | PA | 6-0 | 33-16-17 | D13584 | | | 4 | | | | TB0070Y | C035 | BJ | | 050-099 |
| 183 | 22 | | PA | 7-0 | 33-16-17 | D13584 | | | 4 | | | | TB0070Y | C035 | BJ | | 150-199, 275-299 |
| 184 | 24 | | PK | 5-0 | 21-61-81 | D07972J | | | 6 | | | | D05724J | 21 | | | 050-099 |
| 184 | 24 | | PK | 18-0 | 21-61-81 | D07972J | | | 6 | | | | D05724J | 21 | | | 150-199 |
| 184 | 24 | | PK | 6-0 | 21-61-81 | D07972J | | | 6 | | | | D05724J | 21 | | | 275-299 |
| 185 | 24 | | PK | 3-0 | 21-61-81 | D07972J | | | 14 | | | | TB0102X | C010 | BJ | | 050-099, 275-299 |
| 185 | 24 | | PK | 4-0 | 21-61-81 | D07972J | | | 14 | | | | TB0102X | C010 | BJ | | 150-199 |
| 188 | 20 | | PA | 7-0 | 73-21-11 | GD04438 | | | | | | | D11802 | 3 | | | 050-099, 162-199, 277-278 |
| 188 | 20 | | PA | 6-0 | 73-21-11 | GD04438 | | | | | | | D11802 | 3 | | | 150-154 |
| 188 | 20 | | PA | 8-0 | 73-21-11 | GD04438 | | | | | | | D11802 | 3 | | | 155-157, 275-276 |
| 188 | 20 | | PA | 8-0 | 73-21-11 | GD04438 | | | | | | | D11802 | 3 | | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 77

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | | |
| 191 | 20 | | PA | 6-0 | 73-21-11 | D04754J | | 9 | | | | | D11802 | | 4 | | | 050-099, 150-154, 162-199 |
| 191 | 20 | | PA | 7-0 | 73-21-11 | D04754J | | 9 | | | | | D11802 | | 4 | | | 155-157, 275-299 |
| 195 | 20 | | PA | 3-0 | 73-21-11 | D07986J | | 36 | | | | | TB0104X | A010 | | BJ | | 050-099 |
| 195 | 20 | | PA | 3-0 | 73-21-11 | TB0104X | | | A010 | | | | D07986J | | 36 | | | 150-199, 275-299 |
| 196 | 20 | | PA | 3-0 | 73-21-11 | D07986J | | 35 | | | | | TB0104X | B010 | | BJ | | 050-099 |
| 196 | 20 | | PA | 3-0 | 73-21-11 | TB0104X | | | B010 | | | | D07986J | | 35 | | | 150-199, 275-299 |
| 201B | 24 | | PL | IA | 15-0 | 21-61-11 | D00490 | | 7 | | | | D05724J | | 10 | | | ALL |
| 201R | 24 | | PL | IA | 0-0 | 21-61-11 | D00490 | | 5 | | | | D05724J | | 11 | | | ALL |
| 202B | 20 | | PB | IB | 4-0 | 21-65-11 | D04994J | | 7 | | | | D05406J | | 13 | | | ALL |
| 202R | 20 | | PB | IB | 0-0 | 21-65-11 | D04994J | | 8 | | | | D05406J | | 14 | | | ALL |
| 203B | 20 | | PB | IC | 4-0 | 21-65-11 | D05124J | | 5 | | | | D05406J | | 15 | | | ALL |
| 203R | 20 | | PB | IC | 0-0 | 21-65-11 | D05124J | | 6 | | | | D05406J | | 16 | | | ALL |
| 204B | 20 | | PB | ID | 4-0 | 21-65-11 | D05124J | | 9 | | | | D05406J | | 17 | | | ALL |
| 204R | 20 | | PB | ID | 0-0 | 21-65-11 | D05124J | | 10 | | | | D05406J | | 18 | | | ALL |
| 208B | 20 | | PB | IH | 6-0 | 21-65-11 | D05124J | | 7 | | | | TB0100X | A002 | | BJ | | ALL |
| 208R | 20 | | PB | IH | 0-0 | 21-65-11 | D05124J | | 8 | | | | TB0100X | A003 | | BJ | | ALL |
| 209B | 24 | | PL | II | 6-0 | 28-41-11 | D10224 | | 16 | | | | TB0106X | D001 | | BJ | | ALL |
| 209R | 24 | | PL | II | 0-0 | 28-41-11 | D10224 | | 15 | | | | TB0106X | D002 | | BJ | | ALL |
| 210B | 24 | | PL | IJ | 6-0 | 36-21-11 | TB0102X | | | B003 | | BJ | D04286J | | 3 | | | ALL |
| 210R | 24 | | PL | IJ | 0-0 | 36-21-11 | TB0102X | | | B002 | | BJ | D04286J | | 4 | | | ALL |
| 212B | 20 | | PB | IL | 4-0 | 21-65-11 | D05124J | | 47 | | | | D05406J | | 37 | | | ALL |
| 212R | 20 | | PB | IL | 0-0 | 21-65-11 | D05124J | | 48 | | | | D05406J | | 38 | | | ALL |
| 213B | 20 | | PB | IM | 5-0 | 21-65-11 | TB0100X | | | D002 | | BJ | D05124J | | 49 | | | 050-099 |
| 213B | 20 | | PB | IM | 6-0 | 21-65-11 | TB0100X | | | D002 | | BJ | D05124J | | 49 | | | 150-199, 275-299 |
| 213R | 20 | | PB | IM | 0-0 | 21-65-11 | TB0100X | | | D003 | | BJ | D05124J | | 50 | | | ALL |
| 230B | 24 | | PL | JE | 15-0 | 28-41-13 | D01374 | | 21 | | | | TB0100X | C005 | | BJ | | ALL |
| 230R | 24 | | PL | JE | 0-0 | 28-41-13 | D01374 | | 19 | | | | TB0100X | D005 | | BJ | | ALL |
| 234B | 22 | | PR | VA | 3-0 | 21-66-21 | D05906J | | 28 | | | | D05124J | | 44 | | | 050-099 |
| 234B | 22 | | PR | AV | 3-0 | 21-66-21 | D05906J | | 28 | | | | D05124J | | 44 | | | 162-199 |
| 234R | 22 | | PR | VA | 0-0 | 21-66-21 | D05906J | | 27 | | | | D05124J | | 43 | | | 050-099 |
| 234R | 22 | | PR | AV | 0-0 | 21-66-21 | D05906J | | 27 | | | | D05124J | | 43 | | | 162-199 |
| 234Z | | | | VA | 0-0 | 21-66-21 | D05906J | | 29 | | | | D05124J | | 42 | | | 050-099 |
| 234Z | | | | AV | 0-0 | 21-66-21 | D05906J | | 29 | | | | D05124J | | 42 | | | 162-199 |
| 301B | 24 | | PM | MA | 15-0 | 21-61-11 | D00490 | | 1 | | | | D05724J | | 12 | | | ALL |
| 301R | 24 | | PM | MA | 0-0 | 21-61-11 | D00490 | | 2 | | | | D05724J | | 13 | | | ALL |
| 301Y | 24 | | PM | MA | 0-0 | 21-61-11 | D00490 | | 3 | | | | D05724J | | 14 | | | ALL |
| 302B | 24 | | PM | MB | 15-0 | 21-61-21 | D00492 | | 1 | | | | D05724J | | 25 | | | ALL |
| 302R | 24 | | PM | MB | 0-0 | 21-61-21 | D00492 | | 2 | | | | D05724J | | 26 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0060
Page 78
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|----------|-------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 302Y | 24 | PM | MB | 0-0 | 21-61-21 | | D00492 | | 3 | | | D05724J | | 27 | | ALL |
| 303B | 24 | PM | MC | 15-0 | 21-61-31 | | D01068 | | 1 | | | D05724J | | 38 | | ALL |
| 303R | 24 | PM | MC | 0-0 | 21-61-31 | | D01068 | | 2 | | | D05724J | | 39 | | ALL |
| 303Y | 24 | PM | MC | 0-0 | 21-61-31 | | D01068 | | 3 | | | D05724J | | 40 | | ALL |
| 307B | 24 | PM | MG | 14-0 | 33-13-17 | | D04994J | | 15 | | | D00842 | | 7 | | ALL |
| 307R | 24 | PM | MG | 0-0 | 33-13-17 | | D04994J | | 16 | | | D00842 | | 8 | | ALL |
| 307Y | 24 | PM | MG | 0-0 | 33-13-17 | | D04994J | | 17 | | | D00842 | | 10 | | ALL |
| 308B | 24 | PM | MH | 10-0 | 33-13-21 | | D10396 | | 11 | | | D10398 | | 5 | | 050-099 |
| 308B | 24 | PM | MH | 8-0 | 33-13-21 | | D10396 | | 11 | | | D10398 | | 5 | | 150-199, 275-299 |
| 308R | 24 | PM | MH | 0-0 | 33-13-21 | | D10396 | | 10 | | | D10398 | | 6 | | ALL |
| 308Y | 24 | PM | MH | 0-0 | 33-13-21 | | D10396 | | 12 | | | D10398 | | 1 | | ALL |
| 313B | 24 | PM | MM | 15-0 | 33-13-18 | | D00842 | | 12 | | | TB0100X | D007 | BJ | | ALL |
| 313R | 24 | PM | MM | 0-0 | 33-13-18 | | D00842 | | 9 | | | TB0100X | D006 | BJ | | ALL |
| 313Y | 24 | PM | MM | 0-0 | 33-13-18 | | D00842 | | 11 | | | TB0100X | D008 | BJ | | ALL |
| 315B | 24 | PM | MO | 15-0 | 21-61-41 | | D10706 | | 1 | | | D05724J | | 46 | | ALL |
| 315R | 24 | PM | MO | 0-0 | 21-61-41 | | D10706 | | 2 | | | D05724J | | 47 | | ALL |
| 315Y | 24 | PM | MO | 0-0 | 21-61-41 | | D10706 | | 3 | | | D05724J | | 48 | | ALL |
| 32A | 24 | PK | | 5-0 | 49-72-11 | | D04754J | | 21 | | | TB0096X | D004 | BJ | | 050-099 |
| 32A | 24 | PK | | 5-0 | 49-72-11 | | TB0096X | D004 | BJ | | | D04754J | | 21 | | 162-199, 275-299 |
| 338B | 24 | PM | AR | 12-0 | 21-61-61 | | D00492 | | 4 | | | TB0096X | A003 | BJ | | 050-099 |
| 338B | 24 | PM | IE | 13-0 | 21-61-61 | | D00492 | | 4 | | | TB0096X | A003 | BJ | | 150-199, 275-299 |
| 338R | 24 | PM | AR | 0-0 | 21-61-61 | | D00492 | | 5 | | | TB0096X | B003 | BJ | | 050-099 |
| 338R | 24 | PM | IE | 0-0 | 21-61-61 | | D00492 | | 5 | | | TB0096X | B003 | BJ | | 150-199, 275-299 |
| 338Y | 24 | PM | AR | 0-0 | 21-61-61 | | D00492 | | 6 | | | TB0096X | C003 | BJ | | 050-099 |
| 338Y | 24 | PM | IE | 0-0 | 21-61-61 | | D00492 | | 6 | | | TB0096X | C003 | BJ | | 150-199, 275-299 |
| 339B | 24 | PM | AS | 8-0 | 21-61-71 | | D10706 | | 4 | | | TB0066X | B014 | BJ | | 050-099 |
| 339B | 24 | PM | IF | 8-0 | 21-61-71 | | D10706 | | 4 | | | TB0066X | B014 | BJ | | 150-199, 275-299 |
| 339R | 24 | PM | AS | 0-0 | 21-61-71 | | D10706 | | 5 | | | TB0066X | C014 | BJ | | 050-099 |
| 339R | 24 | PM | IF | 0-0 | 21-61-71 | | D10706 | | 5 | | | TB0066X | C014 | BJ | | 150-199, 275-299 |
| 339Y | 24 | PM | AS | 0-0 | 21-61-71 | | D10706 | | 6 | | | TB0066X | D014 | BJ | | 050-099 |
| 339Y | 24 | PM | IF | 0-0 | 21-61-71 | | D10706 | | 6 | | | TB0066X | D014 | BJ | | 150-199, 275-299 |
| 403B | 24 | PN | QC | 5-0 | 24-23-11 | | D05846P | | 8 | | | D04794J | | 19 | | ALL |
| 403G | 24 | PN | QC | 0-0 | 24-23-11 | | D05846P | | 5 | | | D04794J | | 22 | | ALL |
| 403R | 24 | PN | QC | 0-0 | 24-23-11 | | D05846P | | 7 | | | D04794J | | 20 | | ALL |
| 403Y | 24 | PN | QC | 0-0 | 24-23-11 | | D05846P | | 6 | | | D04794J | | 21 | | ALL |
| 407R | 22 | PH | | 6-0 | 26-18-12 | | D10224 | | 17 | | | TB0102X | A009 | BJ | | ALL |
| 410R | 22 | PH | | 6-0 | 26-18-22 | | TB0100D | A010 | 2 | | | D04650J | | 9 | | 050-099 |
| 410R | 22 | PH | | 5-0 | 26-18-22 | | TB0100Y | A011 | BJ | | | D04650J | | 9 | | 150-157, 275-299 |
| 410R | 22 | PH | | 5-0 | 26-18-22 | | TB0100D | A010 | 2 | | | D04650J | | 9 | | 162-199 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 79

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 411R | 22 | | PH | | 5-0 | 26-18-22 | D10224 | | 6 | | D04650J | | 10 | | 050-099 |
| 411R | 22 | | PH | | 6-0 | 26-18-22 | D10224 | | 6 | | D04650J | | 10 | | 150-199, 275-299 |
| 412R | 22 | | PH | | 6-0 | 26-18-12 | D10224 | | 20 | | TB0102X | C008 | BJ | | ALL |
| 413R | 22 | | PH | | 6-0 | 26-18-12 | D10224 | | 1 | | TB0102X | D008 | BJ | | ALL |
| 414R | 22 | | PH | | 6-0 | 26-18-22 | TB0102X | B009 | BJ | | D04650J | | 48 | | 050-099, 150-199 |
| 414R | 22 | | PH | | 5-0 | 26-18-22 | TB0102X | B009 | BJ | | D04650J | | 48 | | 275-299 |
| 415R | 22 | | PH | | 6-0 | 26-18-22 | D10224 | | 4 | | D04650J | | 49 | | ALL |
| 501 | 20 | | PA | | 5-0 | 24-51-72 | D05906J | | 1 | | TB0100Y | C011 | BJ | | 050-099, 162-164, 276 |
| 502 | 20 | | PA | | 5-0 | 24-51-72 | D04794J | | 10 | | TB0102X | B007 | BJ | | 050-099, 162-164, 276 |
| 503 | 22 | | PQ | SD | 8-0 | 33-16-17 | TB0066Y | | C035 | BJ | D01342 | | 3 | | ALL |
| 503Z | | | | SD | 0-0 | 33-16-17 | TB0066Y | | DED | | D01342 | | DED | | ALL |
| 504 | 22 | | PA | | 8-0 | 33-16-17 | TB0066Z | | 28 | BJ | D01342 | | 4 | | ALL |
| 505 | 22 | | PA | | 15-0 | 21-61-11 | D01342 | | 5 | | D05724J | | 4 | | ALL |
| 506 | 22 | | PA | | 14-0 | 21-61-21 | D01342 | | 6 | | TB0102Y | A038 | BJ | | ALL |
| 507 | 22 | | PA | | 14-0 | 21-61-31 | D01342 | | 7 | | TB0102Y | C036 | BJ | | ALL |
| 508 | 24 | | PK | | 13-0 | 21-61-11 | D01342 | | 8 | | TB0102Y | A035 | BJ | | ALL |
| 509 | 20 | | PA | | 7-0 | 33-13-16 | D12176 | | 1 | | TB0064G | | 6 | 2 | 050-099, 155-199, 276-299 |
| 50A | 24 | | PK | | 5-0 | 21-25-21 | D07972J | | 1 | | D04766J | | 23 | | ALL |
| 50B | 22 | | PA | | 6-0 | 21-25-21 | TB0102Y | A040 | BJ | | D04766J | | 25 | | ALL |
| 50C | 22 | | PA | | 6-0 | 21-25-21 | TB0102Y | A040 | BJ | | D04766J | | 60 | | ALL |
| 50D | 24 | | PK | | 5-0 | 21-26-11 | D07972J | | 2 | | D04766J | | 46 | | ALL |
| 50E | 20 | | PA | | 6-0 | 21-31-21 | TB0066X | C005 | BJ | | D05006P | | 1 | | ALL |
| 50F | 20 | | PA | | 6-0 | 21-31-21 | TB0100Y | A016 | BJ | | D05356J | | 14 | | ALL |
| 50G | 24 | | PK | | 11-0 | 21-44-11 | TB0066Y | A015 | BJ | | D05062J | | 12 | | ALL |
| 50H | 24 | | PK | | 6-0 | 21-44-21 | D05006P | | 6 | | TB0066Y | C019 | BJ | | ALL |
| 50J | 24 | | PK | | 11-0 | 21-44-21 | TB0066Y | C019 | BJ | | D04870J | | 21 | | ALL |
| 50M | 22 | | PQ | RG | 6-0 | 21-33-11 | TB0100Z | | 20 | BJ | D04650J | | 2 | | ALL |
| 50MZ | | | | RG | 0-0 | 21-33-11 | TB0100Z | | DED | | D04650J | | DED | | ALL |
| 50N | 24 | | PK | | 13-0 | 21-43-11 | D05062J | | 8 | | D05006P | | 2 | | ALL |
| 50T | 20 | | PA | | 3-0 | 21-45-11 | D04972P | | 13 | | D04970P | | 2 | | ALL |
| 50U | 20 | | PA | | 3-0 | 21-45-11 | D04972P | | 14 | | D04970P | | 3 | | ALL |
| 50V | 24 | | PK | | 5-0 | 21-51-21 | D07972J | | 3 | | D04650J | | 18 | | ALL |
| 50W | 24 | | PK | | 5-0 | 21-51-13 | D07972J | | 4 | | D04286J | | 13 | | ALL |
| 50X | 24 | | PK | | 5-0 | 21-51-13 | D07972J | | 5 | | D04286J | | 14 | | ALL |
| 50Y | 24 | | PK | | 6-0 | 21-44-11 | D05006P | | 4 | | TB0066Y | A015 | BJ | | ALL |
| 50Z | 24 | | PK | | 5-0 | 21-53-21 | D05062J | | 5 | | D07972J | | 8 | | ALL |
| 510 | 20 | | PA | | 6-0 | 33-13-16 | D12176 | | 2 | | GD00112 | | A.. | 2 | 050-099, 155-199, 276-299 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 80
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 511 | 22 | PA | | | 13-0 | 21-61-41 | D01342 | | 11 | | | TB0102Y | A034 | BJ | | ALL |
| 513 | 22 | PA | | | 15-0 | 21-51-21 | D01342 | | 13 | | | D04650J | 24 | | | ALL |
| 514 | 22 | PA | | | 15-0 | 21-51-21 | D01342 | | 14 | | | D04650J | 23 | | | ALL |
| 515 | 24 | PK | | | 15-0 | 21-51-21 | D01342 | | 15 | | | D04650J | 22 | | | ALL |
| 516 | 24 | PK | | | 14-0 | 21-25-21 | D01342 | | 16 | | | D04766J | 24 | | | ALL |
| 517 | 22 | PA | | | 14-0 | 21-25-21 | D01342 | | 17 | | | TB0102Y | A040 | BJ | | ALL |
| 518 | 24 | PK | | | 14-0 | 21-53-21 | D01342 | | 18 | | | D07972J | 7 | | | ALL |
| 519 | 24 | PK | | | 15-0 | 21-53-21 | D01342 | | 19 | | | D05356J | 10 | | | ALL |
| 51A | 24 | PK | | | 4-0 | 21-53-12 | D07972J | | 9 | | | TB0102Y | C039 | BJ | | ALL |
| 51B | 24 | PK | | | 6-0 | 21-53-12 | D04650J | | 47 | | | TB0102Y | C039 | BJ | | ALL |
| 51C | 24 | PK | | | 6-0 | 21-53-12 | D04870J | | 6 | | | TB0102Y | C039 | BJ | | ALL |
| 51D | 24 | PK | | | 5-0 | 21-53-12 | D07972J | | 10 | | | D05062J | 20 | | | ALL |
| 51E | 24 | PK | | | 4-0 | 21-58-11 | TB0102Y | A030 | | BJ | | D07972J | 11 | | | 050-099 |
| 51E | 24 | PK | | | 4-0 | 21-58-11 | D07972J | | 11 | | | TB0102Y | A030 | BJ | | 150-199, 275-299 |
| 51F | 24 | PK | | | 11-0 | 21-58-11 | TB0066Y | A022 | | BJ | | D04766J | 45 | | | ALL |
| 51G | 24 | PK | | | 11-0 | 21-58-11 | TB0066Y | C015 | | BJ | | D04766J | 49 | | | ALL |
| 51J | 24 | PK | | | 5-0 | 21-58-14 | D07972J | | 15 | | | D05764J | 9 | | | ALL |
| 51K | 22 | PA | | | 6-0 | 21-58-11 | D04766J | | 52 | | | TB0102Y | C015 | BJ | | ALL |
| 51S | 24 | PK | | | 5-0 | 21-58-15 | D07972J | | 16 | | | D04766J | 40 | | | ALL |
| 51V | 12 | PA | | | 7-0 | 21-58-15 | D05920P | | 12 | | | D05928J | 1 | | | ALL |
| 51W | 12 | PA | | | 7-0 | 21-58-15 | D05920P | | 11 | | | D05928J | 2 | | | ALL |
| 51X | 12 | PA | | | 7-0 | 21-58-15 | D05920P | | 10 | | | D05928J | 3 | | | ALL |
| 51Y | 24 | PK | | | 4-0 | 21-58-16 | D07972J | | 17 | | | TB0102Y | C032 | BJ | | ALL |
| 51Z | 24 | PK | | | 6-0 | 21-58-16 | D04766J | | 20 | | | TB0102Y | C032 | BJ | | ALL |
| 520 | 24 | PK | | | 14-0 | 21-53-12 | D01342 | | 20 | | | D04766J | 34 | | | ALL |
| 521 | 22 | PQ | AU | | 6-0 | 28-22-31 | TB0104X | A037 | | BJ | | D07972J | 29 | | | 050-099 |
| 521 | 22 | PQ | AY | | 4-0 | 28-22-31 | TB0104X | A037 | | BJ | | D07972J | 29 | | | 150-199, 275-299 |
| 521Z | | | AU | | 0-0 | 28-22-31 | TB0104X | DED | | | | D07972J | DED | | | 050-099 |
| 521Z | | | AY | | 0-0 | 28-22-31 | TB0104X | DED | | | | D07972J | DED | | | 150-199, 275-299 |
| 522 | 24 | PK | | | 14-0 | 21-53-12 | D01342 | | 22 | | | D04766J | 36 | | | ALL |
| 523 | 24 | PK | | | 14-0 | 21-53-12 | D01342 | | 23 | | | D04766J | 37 | | | ALL |
| 524 | 24 | PK | | | 14-0 | 21-53-12 | D01342 | | 24 | | | D04766J | 38 | | | ALL |
| 525 | 22 | PA | | | 7-0 | 33-16-17 | D12176 | | 3 | | | TB0066Z | 27 | BJ | | 050-099, 155-199, 276-299 |
| 526 | 22 | PA | | | 7-0 | 33-16-17 | D12176 | | 4 | | | TB0066Z | 29 | BJ | | 050-099, 155-199, 276-299 |
| 527 | 20 | PA | | | 7-0 | 21-25-21 | D01342 | | 27 | | | GD00104 | D.. | 2 | | ALL |
| 528 | 22 | PQ | AV | | 9-0 | 28-22-31 | TB0104X | C037 | | BJ | | D05356J | 12 | | | 050-099 |
| 528 | 22 | PQ | AZ | | 7-0 | 28-22-31 | TB0104X | C037 | | BJ | | D05356J | 12 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 81

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 528Z | | | | AV | 0-0 | 28-22-31 | TB0104X | DED | | | D05356J | DED | | | 050-099 |
| 528Z | | | | AZ | 0-0 | 28-22-31 | TB0104X | DED | | | D05356J | DED | | | 150-199, 275-299 |
| 529 | 24 | PK | | | 15-0 | 21-51-21 | D01342 | 29 | | | D04650J | 21 | | | ALL |
| 52A | 22 | PA | | | 5-0 | 21-58-16 | TB0102Y | C037 | BJ | | D04870J | 54 | | | 050-099 |
| 52A | 22 | PA | | | 6-0 | 21-58-16 | TB0102Y | C037 | BJ | | D04870J | 54 | | | 150-199, 275-299 |
| 52B | 24 | PK | | | 7-0 | 21-58-16 | TB0102Y | C037 | BJ | | D05406J | 36 | | | ALL |
| 52C | 22 | PA | | | 6-0 | 21-58-16 | TB0102Y | C037 | BJ | | D04766J | 21 | | | ALL |
| 52D | 24 | PK | | | 13-0 | 21-58-16 | D04970P | 12 | | | D04870J | 8 | | | ALL |
| 52E | 24 | PK | | | 13-0 | 21-58-16 | D04970P | 13 | | | D04870J | 9 | | | ALL |
| 52F | 24 | PK | | | 13-0 | 21-58-16 | D04970P | 14 | | | D04870J | 35 | | | ALL |
| 52G | 24 | PK | | | 13-0 | 21-58-16 | D04970P | 11 | | | D04870J | 50 | | | ALL |
| 52H | 24 | PK | | | 4-0 | 21-61-11 | D07972J | 19 | | | TB0102Y | A016 | BJ | | ALL |
| 52J | 24 | PK | | | 6-0 | 21-61-11 | D05724J | 3 | | | TB0102Y | A016 | BJ | | ALL |
| 52K | 24 | PK | | | 4-0 | 21-61-11 | D07972J | 20 | | | TB0102Y | A036 | BJ | | ALL |
| 52L | 24 | PK | | | 6-0 | 21-61-11 | TB0102Y | A036 | BJ | | D05724J | 5 | | | ALL |
| 52M | 24 | PK | | | 5-0 | 21-61-11 | D04994J | 12 | | | TB0102Y | A035 | BJ | | ALL |
| 52N | 24 | PK | | | 6-0 | 21-61-21 | D07972J | 21 | | | D05724J | 16 | | | ALL |
| 52P | 24 | PK | | | 6-0 | 21-61-21 | D07972J | 22 | | | D05724J | 18 | | | ALL |
| 52R | 22 | PA | | | 6-0 | 21-61-21 | D05124J | 4 | | | TB0102Y | A038 | BJ | | ALL |
| 52S | 22 | PA | | | 6-0 | 21-61-21 | D05724J | 28 | | | TB0102Y | A038 | BJ | | ALL |
| 52T | 18 | PA | | | 5-0 | 32-71-11 | D07972J | 18 | DL | | D05062J | 14 | DK | | 150-199, 275-299 |
| 52U | 24 | PK | | | 6-0 | 21-61-31 | D07972J | 23 | | | D05724J | 29 | | | ALL |
| 52V | 24 | PK | | | 6-0 | 21-61-31 | D07972J | 24 | | | D05724J | 31 | | | ALL |
| 52W | 22 | PA | | | 6-0 | 21-61-31 | D05124J | 3 | | | TB0102Y | C036 | BJ | | ALL |
| 52X | 22 | PA | | | 6-0 | 21-61-31 | D05724J | 41 | | | TB0102Y | C036 | BJ | | ALL |
| 52Z | 24 | PK | | | 6-0 | 24-22-21 | TB0104X | B004 | BJ | | D04794J | 14 | | | ALL |
| 530 | 22 | PQ | AW | | 9-0 | 28-22-31 | TB0104X | B037 | BJ | | D05356J | 13 | | | 050-099 |
| 530 | 22 | PQ | BQ | | 7-0 | 28-22-31 | TB0104X | B037 | BJ | | D05356J | 13 | | | 150-199, 275-299 |
| 530Z | | | AW | | 0-0 | 28-22-31 | TB0104X | DED | | | D05356J | DED | | | 050-099 |
| 530Z | | | BQ | | 0-0 | 28-22-31 | TB0104X | DED | | | D05356J | DED | | | 150-199, 275-299 |
| 531 | 20 | PA | | | 7-0 | 21-53-12 | D01342 | 31 | | | GD00104 | D.. | 2 | | ALL |
| 532 | 24 | PK | | | 15-0 | 21-61-51 | D01342 | 32 | | | D05406J | 3 | | | ALL |
| 533 | 24 | PK | | | 14-0 | 21-61-51 | D01342 | 33 | | | TB0102X | C002 | BJ | | ALL |
| 534 | 24 | PK | | | 14-0 | 21-61-51 | D01342 | 34 | | | D04766J | 56 | | | ALL |
| 535 | 22 | PQ | BA | | 9-0 | 28-22-31 | TB0104X | D037 | BJ | | D05356J | 1 | | | 050-099 |
| 535 | 22 | PQ | BU | | 7-0 | 28-22-31 | TB0104X | D037 | BJ | | D05356J | 1 | | | 150-199, 275-299 |
| 535Z | | | BA | | 0-0 | 28-22-31 | TB0104X | DED | | | D05356J | DED | | | 050-099 |
| 535Z | | | BU | | 0-0 | 28-22-31 | TB0104X | DED | | | D05356J | DED | | | 150-199, 275-299 |
| 536 | 22 | PQ | BE | | 6-0 | 28-22-31 | TB0104X | A038 | BJ | | D07972J | 30 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 82

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 536 | 22 | PQ | BV | | 4-0 | 28-22-31 | TB0104X | A038 | BJ | | D07972J | 30 | | | 150-199, 275-299 |
| 536Z | | | BE | | 0-0 | 28-22-31 | TB0104X | DED | | | D07972J | DED | | | 050-099 |
| 536Z | | | BV | | 0-0 | 28-22-31 | TB0104X | DED | | | D07972J | DED | | | 150-199, 275-299 |
| 537 | 20 | PQ | BF | | 9-0 | 28-22-31 | TB0104X | B038 | BJ | | D05356J | 8 | | | 050-099 |
| 537 | 20 | PQ | BW | | 7-0 | 28-22-31 | TB0104X | B038 | BJ | | D05356J | 8 | | | 150-199, 275-299 |
| 537Z | | | BF | | 0-0 | 28-22-31 | TB0104X | DED | | | D05356J | DED | | | 050-099 |
| 537Z | | | BW | | 0-0 | 28-22-31 | TB0104X | DED | | | D05356J | DED | | | 150-199, 275-299 |
| 538 | 20 | PQ | BG | | 9-0 | 28-22-31 | TB0104X | C038 | BJ | | D05356J | 11 | | | 050-099 |
| 538 | 20 | PQ | BX | | 7-0 | 28-22-31 | TB0104X | C038 | BJ | | D05356J | 11 | | | 150-199, 275-299 |
| 538Z | | | BG | | 0-0 | 28-22-31 | TB0104X | DED | | | D05356J | DED | | | 050-099 |
| 538Z | | | BX | | 0-0 | 28-22-31 | TB0104X | DED | | | D05356J | DED | | | 150-199, 275-299 |
| 539 | 20 | PA | | | 11-0 | 78-34-21 | D04758J | | | GB | GD04442 | S.. | 2 | | ALL |
| 53E | 24 | PK | | | 5-0 | 24-11-21 | D07974J | 16 | | | D04794J | 16 | | | ALL |
| 53F | 20 | PA | | | 4-0 | 24-41-11 | D07974J | 18 | | | TB0096X | D002 | BJ | | ALL |
| 53G | 24 | PV | XB | | 6-0 | 24-51-31 | D04794J | 4 | | | TB0106Y | A011 | BJ | | ALL |
| 53GZ | | | XB | | 0-0 | 24-51-31 | D04794J | DED | | | TB0106Y | DED | | | ALL |
| 53H | 24 | PV | XC | | 6-0 | 24-51-31 | D04794J | 1 | | | TB0106Y | C011 | BJ | | ALL |
| 53HZ | | | XC | | 0-0 | 24-51-31 | D04794J | DED | | | TB0106Y | DED | | | ALL |
| 53J | 24 | PV | XA | | 6-0 | 24-51-31 | D04794J | 24 | | | TB0106Y | C011 | BJ | | ALL |
| 53JZ | | | XA | | 0-0 | 24-51-31 | D04794J | DED | | | TB0106Y | DED | | | ALL |
| 53K | 24 | PK | | | 7-0 | 24-51-41 | D05846P | 9 | | | D05406J | 22 | | | 050-099 |
| 53K | 24 | PK | | | 7-0 | 24-51-43 | D05846P | 9 | | | D05406J | 22 | | | 150-199, 275-299 |
| 53L | 22 | PA | | | 3-0 | 24-51-51 | D04794J | 25 | | | D05124J | 24 | | | ALL |
| 53M | 22 | PA | | | 3-0 | 24-51-51 | D04794J | 26 | | | D05124J | 27 | | | ALL |
| 53N | 22 | PA | | | 3-0 | 24-51-51 | D04794J | 34 | | | D05124J | 26 | | | ALL |
| 53P | 24 | PK | | | 6-0 | 24-51-71 | TB0102Y | C016 | BJ | | D05416J | 23 | | | ALL |
| 53R | 24 | PK | | | 6-0 | 24-51-71 | TB0100Y | C034 | BJ | | D05416J | 22 | | | ALL |
| 53T | 22 | PA | | | 6-0 | 25-31-11 | D04794J | 5 | | | TB0102X | A003 | BJ | | ALL |
| 53U | 22 | PA | | | 8-0 | 25-29-11 | D07974J | 21 | | | D05846P | 13 | | | ALL |
| 53V | 22 | PA | | | 6-0 | 27-13-11 | TB0102Y | A033 | BJ | | D05416J | 3 | | | ALL |
| 53W | 22 | PA | | | 6-0 | 27-13-11 | TB0102Y | A033 | BJ | | D05406J | 5 | | | ALL |
| 53X | 18 | PA | | | 4-0 | 27-51-11 | TB0096G | 20 | 2 | | D07976J | 8 | DL | | ALL |
| 53Y | 18 | PA | | | 6-0 | 27-51-11 | TB0096G | 20 | 2 | | D04758J | 7 | DK | | ALL |
| 53Z | 18 | PA | | | 6-0 | 27-51-11 | TB0096G | 20 | 2 | | D04760J | 32 | DK | | ALL |
| 541 | 20 | PQ | AD | | 11-0 | 78-34-21 | TB0104X | C009 | BJ | | D04758J | 17 | | | ALL |
| 541Z | | | AD | | 0-0 | 78-34-21 | TB0104X | | | GE | D04758J | | | GB | ALL |
| 542 | 22 | PA | | | 6-0 | 21-61-41 | D05724J | 42 | | | TB0102Y | A034 | BJ | | ALL |
| 543 | 24 | PK | | | 6-0 | 21-61-41 | D07972J | 12 | | | D05724J | 43 | | | ALL |
| 545 | 24 | PK | | | 6-0 | 21-61-41 | D07972J | 13 | | | D05724J | 45 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 83

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 546 | 22 | PA | | | 6-0 | 21-61-41 | D05124J | | 46 | | | TB0102Y | A034 | BJ | | ALL |
| 54A | 22 | PA | | | 5-0 | 27-51-11 | D04760J | | 33 | | | D04758J | | 8 | | ALL |
| 54B | 18 | PA | | | 5-0 | 27-51-11 | D04760J | | 34 | DK | | D04758J | | 9 | DK | ALL |
| 54C | 20 | PA | | | 5-0 | 27-51-11 | D04760J | | 35 | | | D04758J | | 10 | | ALL |
| 54E | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 36 | | | D04758J | | 21 | | ALL |
| 54F | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 37 | | | D04758J | | 22 | | ALL |
| 54G | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 38 | | | D04758J | | 23 | | ALL |
| 54H | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 39 | | | D04758J | | 24 | | ALL |
| 54J | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 40 | | | D04758J | | 25 | | ALL |
| 54K | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 41 | | | D04758J | | 26 | | ALL |
| 54L | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 42 | | | D04758J | | 27 | | ALL |
| 54M | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 43 | | | D04758J | | 28 | | ALL |
| 54N | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 44 | | | D04758J | | 35 | | ALL |
| 54P | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 45 | | | D04758J | | 36 | | ALL |
| 54R | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 46 | | | D04758J | | 37 | | ALL |
| 54S | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 47 | | | D04758J | | 41 | | ALL |
| 54T | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 48 | | | D04758J | | 42 | | ALL |
| 54U | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 49 | | | D04758J | | 43 | | ALL |
| 54V | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 50 | | | D04758J | | 44 | | ALL |
| 54W | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 51 | | | D04758J | | 45 | | ALL |
| 54X | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 52 | | | D04758J | | 46 | | ALL |
| 54Y | 24 | PK | | | 5-0 | 27-51-11 | D04760J | | 53 | | | D04758J | | 47 | | ALL |
| 55A | 24 | PK | | | 5-0 | 27-51-61 | D07976J | | 14 | | | D04758J | | 20 | | ALL |
| 55B | 24 | PK | | | 5-0 | 27-51-61 | D07976J | | 15 | | | D04758J | | 19 | | ALL |
| 55C | 24 | PK | | | 5-0 | 27-58-21 | D07976J | | 19 | | | D04758J | | 2 | | ALL |
| 55E | 18 | PA | | | 4-0 | 27-81-11 | TB0096G | | 19 | 2 | | D07976J | | 6 | DL | ALL |
| 55F | 18 | PA | | | 6-0 | 27-81-11 | TB0096G | | 19 | 2 | | D04758J | | 11 | DK | ALL |
| 55G | 18 | PA | | | 6-0 | 27-81-11 | TB0096G | | 19 | 2 | | D04760J | | 54 | DK | ALL |
| 55H | 18 | PA | | | 4-0 | 27-81-21 | TB0096G | | 18 | 2 | | D07976J | | 7 | DL | ALL |
| 55J | 18 | PA | | | 6-0 | 27-81-21 | TB0096G | | 18 | 2 | | D04758J | | 15 | DK | ALL |
| 55K | 18 | PA | | | 6-0 | 27-81-21 | TB0096G | | 18 | 2 | | D04754J | | 4 | DK | ALL |
| 55L | 18 | PQ | RL | | 5-0 | 28-41-12 | D04870J | | 2 | DK | | D07988J | | 11 | DL | ALL |
| 55LZ | | | RL | | 0-0 | 28-41-12 | D04870J | | DED | | | D07988J | | DED | | ALL |
| 55M | 24 | PK | | | 6-0 | 28-42-31 | TB0102X | | C005 | BJ | | D05356J | | 18 | | ALL |
| 55P | 22 | PA | | | 4-0 | 29-11-21 | D07978J | | 1 | | | TB0104Y | A013 | BJ | | ALL |
| 55R | 22 | PA | | | 6-0 | 29-11-21 | D04754J | | 16 | | | TB0104Y | C013 | BJ | | ALL |
| 55S | 24 | PK | | | 5-0 | 29-31-11 | D07988J | | 10 | | | D04650J | | 42 | | ALL |
| 55T | 22 | PQ | TO | | 6-0 | 29-32-11 | D04794J | | 36 | | | TB0102Y | A029 | BJ | | ALL |
| 55TZ | | | TO | | 0-0 | 29-32-11 | D04794J | | DED | | | TB0102Y | | DED | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0060
 Page 84
 Jan 21/2005



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 55U | 22 | PQ | TM | | 6-0 | 29-32-11 | D05406J | | 23 | | | TB0102Y | A029 | BJ | | ALL |
| 55UZ | | | TM | | 0-0 | 29-32-11 | D05406J | | DED | | | TB0102Y | DED | | | ALL |
| 55V | 22 | PQ | TP | | 6-0 | 29-32-11 | D04794J | | 35 | | | TB0102Y | C029 | BJ | | ALL |
| 55VZ | | | TP | | 0-0 | 29-32-11 | D04794J | | DED | | | TB0102Y | DED | | | ALL |
| 55W | 22 | PQ | TN | | 6-0 | 29-32-11 | D05406J | | 24 | | | TB0102Y | C029 | BJ | | ALL |
| 55WZ | | | TN | | 0-0 | 29-32-11 | D05406J | | DED | | | TB0102Y | DED | | | ALL |
| 55X | 24 | PV | ZY | | 3-0 | 29-33-11 | D07978J | | 2 | | | TB0102Y | A015 | BJ | | ALL |
| 55XZ | | | ZY | | 0-0 | 29-33-11 | D07978J | | DED | | | TB0102Y | DED | | | ALL |
| 55Y | 24 | PV | AA | | 5-0 | 29-33-11 | D04870J | | 29 | | | TB0102Y | A015 | BJ | | ALL |
| 55YZ | | | AA | | 0-0 | 29-33-11 | D04870J | | DED | | | TB0102Y | DED | | | ALL |
| 55Z | 24 | PK | | | 5-0 | 24-51-52 | D07974J | | 20 | | | D05416J | | | | ALL |
| 564 | 22 | PA | | | 14-0 | 74-31-21 | D00850 | | 4 | | | D04760J | | | | ALL |
| 568 | 24 | PK | | | 17-0 | 80-11-21 | D00850 | | 8 | | | D06156P | | | | ALL |
| 56A | 22 | PA | | | 4-0 | 30-11-11 | D07974J | | 26 | | | TB0102Z | | BJ | | ALL |
| 56B | 22 | PA | | | 6-0 | 30-11-11 | D05656J | | 6 | | | TB0102Z | | BJ | | ALL |
| 56C | 22 | PA | | | 15-0 | 30-11-11 | D05906J | | 18 | | | D10220 | | | | 050-099, 150-199 |
| 56C | 22 | PA | | | 6-0 | 30-11-11 | D05656J | | 7 | | | TB0102X | A005 | BJ | | 275-299 |
| 56D | 24 | PK | | | 6-0 | 30-21-11 | D04972P | | 19 | | | TB0066Y | A018 | BJ | | 050-099, 150-199 |
| 56D | 24 | PK | | | 6-0 | 30-21-11 | D04972P | | 7 | | | TB0066Y | A018 | BJ | | 275-299 |
| 56E | 24 | PK | | | 11-0 | 30-21-11 | D05406J | | 34 | | | TB0066Y | A017 | BJ | | ALL |
| 56F | 24 | PK | | | 5-0 | 30-31-21 | D07974J | | 27 | | | D05906J | | | | ALL |
| 56G | 22 | PA | | | 7-0 | 30-31-21 | D06192P | | 11 | | | D05356J | | | | ALL |
| 56J | 22 | PA | | | 7-0 | 30-31-23 | D06192P | | 13 | | | D05356J | | | | ALL |
| 56K | 22 | PA | | | 3-0 | 30-32-21 | D05906J | | 17 | | | D05656J | | | | ALL |
| 56L | 22 | PA | | | 6-0 | 30-32-21 | D06192P | | 15 | | | D05656J | | | | ALL |
| 56N | 22 | PA | | | 5-0 | 30-34-21 | D06192P | | 18 | | | D05656J | | | | ALL |
| 56P | 22 | PA | | | 6-0 | 30-41-12 | TB0102Y | | | A031 | BJ | D05406J | | | | ALL |
| 56R | 22 | PA | | | 6-0 | 30-41-12 | TB0102Y | | | A031 | BJ | D05356J | | | | ALL |
| 56S | 22 | PA | | | 6-0 | 30-41-12 | TB0102Y | | | C031 | BJ | D05406J | | | | ALL |
| 56T | 22 | PA | | | 6-0 | 30-41-12 | TB0102Y | | | C031 | BJ | D05356J | | | | ALL |
| 56U | 24 | PK | | | 6-0 | 30-41-12 | TB0100Y | | | C014 | BJ | D05356J | | | | ALL |
| 56V | 22 | PQ | SR | | 6-0 | 30-43-11 | D04970P | | 1 | | | TB0070X | A005 | BJ | | ALL |
| 56VZ | | | SR | | 0-0 | 30-43-11 | D04970P | | DED | | | TB0070X | DED | | | ALL |
| 56W | 24 | PK | | | 11-0 | SPARE | D05406J | | 35 | | | TB0066Y | A018 | BJ | | 050-099, 155-199 |
| 56W | 24 | PK | | | 11-0 | 30-21-11 | D05406J | | 35 | | | TB0066Y | A018 | BJ | | 275-299 |
| 570 | 22 | PA | | | 14-0 | 74-31-21 | D00850 | | 10 | | | D05006P | | | | 050-099 |
| 570 | 22 | PA | | | 7-0 | 74-31-21 | D00850 | | 10 | | | D05006P | | | | 150-199, 275-299 |
| 571 | 22 | PA | | | 14-0 | SPARE | D00850 | | | CAP | Y | TB0102Y | | | | ALL |
| 572 | 22 | PA | | | 14-0 | 74-31-21 | D00850 | | 12 | | | TB0102Y | A026 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 85

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|----|-----|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | | |
| 57A | 24 | | PK | | 5-0 | 32-09-12 | D07978J | | 18 | | | | D04650J | | 12 | | | ALL |
| 57B | 24 | | PK | | 5-0 | 32-09-21 | D07978J | | 19 | | | | D04766J | | 22 | | | ALL |
| 57C | 22 | | PA | | 5-0 | 32-31-11 | D07978J | | 20 | | | | D04754J | | 6 | | | ALL |
| 57D | 22 | | PA | | 6-0 | 32-31-11 | TB0102Y | A027 | | BJ | | | D04754J | | 5 | | | ALL |
| 57E | 22 | | PA | | 6-0 | 32-31-11 | TB0102Y | A027 | | BJ | | | D04650J | | 1 | | | ALL |
| 57F | 22 | | PA | | 6-0 | 32-31-11 | TB0102Y | A027 | | BJ | | | D04870J | | 1 | | | ALL |
| 57G | 24 | | PK | | 3-0 | 32-41-11 | D07978J | | 23 | | | | TB0102Y | C014 | | BJ | | ALL |
| 57H | 24 | | PK | | 5-0 | 32-41-11 | D04754J | | 8 | | | | TB0102Y | C014 | | BJ | | ALL |
| 57J | 24 | | PK | | 6-0 | 32-41-11 | D04650J | | 3 | | | | TB0102Y | C014 | | BJ | | ALL |
| 57K | 24 | | PK | | 5-0 | 32-42-11 | D07978J | | 21 | | | | D04766J | | 14 | | | ALL |
| 57L | 24 | | PK | | 3-0 | 32-42-12 | D07978J | | 22 | | | | TB0102D | A017 | | 2 | | ALL |
| 57M | 24 | | PK | | 4-0 | 32-42-12 | D04758J | | 34 | | | | D04650J | | 26 | | | ALL |
| 57N | 24 | | PK | | 4-0 | 32-42-12 | D04758J | | 33 | | | | D04650J | | 27 | | | ALL |
| 57P | 24 | | PK | | 4-0 | 32-42-12 | D04758J | | 32 | | | | D04650J | | 25 | | | ALL |
| 57R | 24 | | PK | | 4-0 | 32-42-12 | D04738J | | 19 | | | | D04650J | | 29 | | | ALL |
| 57S | 24 | | PK | | 4-0 | 32-42-12 | D04738J | | 27 | | | | D04650J | | 30 | | | ALL |
| 57T | 24 | | PK | | 4-0 | 32-42-12 | D04738J | | 28 | | | | D04650J | | 31 | | | ALL |
| 57U | 24 | | PK | | 4-0 | 32-42-12 | D04738J | | 29 | | | | D04650J | | 32 | | | ALL |
| 57V | 24 | | PK | | 4-0 | 32-42-12 | D04738J | | 30 | | | | D04650J | | 33 | | | ALL |
| 57W | 24 | | PK | | 4-0 | 32-42-12 | D04738J | | 31 | | | | D04650J | | 34 | | | ALL |
| 57X | 24 | | PK | | 4-0 | 32-42-12 | D04738J | | 26 | | | | D04650J | | 35 | | | ALL |
| 57Y | 24 | | PK | | 5-0 | 32-42-12 | D04738J | | 25 | | | | TB0102D | C012 | | 2 | | ALL |
| 57Z | 24 | | PK | | 4-0 | 32-42-12 | D04738J | | 20 | | | | D04650J | | 37 | | | ALL |
| 581 | 20 | | PA | | 8-0 | 33-13-16 | D00884 | | 1 | | | | TB0064G | | 3 | | 2 | ALL |
| 582 | 20 | | PA | | 7-0 | 33-13-16 | D00884 | | 2 | | | | GD00112 | | A.. | | 2 | ALL |
| 584 | 18 | | PA | | 5-0 | 30-42-11 | D00884 | | 4 | | | | D04970P | | 10 | | | ALL |
| 587 | 18 | | PA | | 8-0 | 30-42-11 | D00884 | | 7 | | | | D05006P | | 21 | | | ALL |
| 588 | 22 | | PA | | 8-0 | 30-43-11 | D05006P | | 33 | | | | D00884 | | 8 | | | ALL |
| 589 | 22 | | PA | | 8-0 | 30-43-11 | D00884 | | 9 | | | | TB0066X | | D005 | | BJ | ALL |
| 58A | 24 | | PK | | 4-0 | 32-42-12 | D04650J | | 40 | | | | D04738J | | 21 | | | ALL |
| 58B | 24 | | PK | | 4-0 | 32-42-12 | D04650J | | 7 | | | | D04738J | | 50 | | | ALL |
| 58C | 24 | | PK | | 4-0 | 32-42-12 | D04650J | | 38 | | | | D04738J | | 23 | | | ALL |
| 58D | 24 | | PK | | 5-0 | 32-42-12 | D04738J | | 24 | | | | TB0102Y | | C027 | | BJ | ALL |
| 58E | 24 | | PK | | 6-0 | 32-42-12 | D05406J | | 29 | | | | TB0102Y | | C027 | | BJ | ALL |
| 58F | 24 | | PK | | 6-0 | 32-42-12 | D04650J | | 39 | | | | TB0102Y | | C027 | | BJ | ALL |
| 58G | 24 | | PK | | 5-0 | 32-42-12 | D04650J | | 36 | | | | TB0102D | | C012 | | 2 | ALL |
| 58H | 20 | | PA | | 4-0 | 32-42-12 | GD04440 | | D.. | | 2 | | TB0102D | | A012 | | 2 | ALL |
| 58N | 20 | | PA | | 6-0 | 33-42-11 | D05006P | | 25 | | | | D04972P | | 25 | | | ALL |
| 58P | 20 | | PA | | 3-0 | 33-42-11 | D04994J | | 11 | | | | D04286J | | 17 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0060
 Page 86
 Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 58R | 20 | | PA | 6-0 | 33-43-11 | D05006P | | 9 | | | | | TB0066X | C006 | BJ | | 050-099 |
| 58R | 18 | | PA | 6-0 | 33-43-11 | D05006P | | 9 | DL | | | | TB0066F | A025 | 2 | | 150-199, 275-299 |
| 58T | 20 | | PA | 6-0 | 33-43-11 | D04972P | | 9 | | | | | TB0066X | D006 | BJ | | 050-099 |
| 58T | 18 | | PA | 6-0 | 33-43-11 | D04972P | | 9 | DK | | | | TB0066F | A026 | 2 | | 150-199, 275-299 |
| 58V | 22 | | PA | 7-0 | 33-45-11 | D04972P | | 4 | | | | | TB0066X | A003 | BJ | | ALL |
| 58W | 18 | | PA | 4-0 | 33-51-11 | D07986J | | 6 | DL | | | | TB0096G | 17 | 2 | | ALL |
| 58X | 18 | | PA | 6-0 | 33-51-11 | TB0096G | | 17 | 2 | | | | D05124J | 14 | DK | | ALL |
| 58Y | 18 | | PA | 5-0 | 33-51-11 | D07986J | | 7 | DL | | | | D05124J | 15 | DK | | ALL |
| 58Z | 24 | | PK | 6-0 | 33-51-11 | TB0106X | | C003 | BJ | | | | D05406J | 2 | | | ALL |
| 590 | 18 | | PA | 5-0 | 30-42-11 | D00884 | | 10 | | | | | D04970P | 7 | | | ALL |
| 59A | 22 | | PA | 6-0 | 33-51-11 | TB0106X | | C004 | BJ | | | | D05124J | 16 | | | ALL |
| 59C | 22 | | PA | 6-0 | 33-51-11 | TB0106X | | C005 | BJ | | | | D05124J | 18 | | | ALL |
| 59D | 16 | | PA | 5-0 | 33-26-21 | D07986J | | 9 | FL | | | | D05124J | 19 | FM | | ALL |
| 59E | 22 | | PA | 5-0 | 33-26-11 | D07986J | | 8 | | | | | D05124J | 20 | | | ALL |
| 59F | 20 | | PA | 3-0 | 33-26-11 | D04870J | | 32 | | | | | D05124J | 28 | | | ALL |
| 59H | 22 | | PA | 5-0 | 33-25-11 | D07978J | | 6 | | | | | TB0102X | A006 | BJ | | ALL |
| 59J | 20 | | PA | 3-0 | 33-26-11 | D04870J | | 4 | | | | | D05124J | 25 | | | 050-099, 150-199 |
| 59L | 20 | | PA | 6-0 | 33-11-14 | D05656J | | 10 | | | | | TB0102Y | A013 | BJ | | ALL |
| 59M | 20 | | PA | 9-0 | 33-11-14 | D06156P | | 2 | | | | | TB0102Y | A013 | BJ | | ALL |
| 59N | 22 | | PA | 5-0 | 33-13-13 | D07986J | | 15 | | | | | D04994J | 13 | | | ALL |
| 59P | 24 | | PK | 5-0 | 33-13-17 | D04994J | | 14 | | | | | D07988J | 15 | | | ALL |
| 59R | 24 | | PK | 5-0 | 33-14-11 | TB0104Y | | A021 | BJ | | | | D07986J | 14 | | | ALL |
| 59S | 24 | | PK | 4-0 | 33-14-31 | D07988J | | 14 | | | | | TB0100Z | 19 | BJ | | ALL |
| 59T | 18 | | PA | 3-0 | 26-13-11 | TB0102F | | A011 | 2 | | | | D07978J | 16 | DL | | 050-099 |
| 59T | 18 | | PA | 3-0 | 26-13-11 | D07978J | | 16 | DL | | | | TB0102F | A011 | 2 | | 150-199 |
| 59V | 24 | | PK | 6-0 | 33-16-11 | D04766J | | 59 | | | | | D06156P | 1 | | | ALL |
| 59W | 22 | | PA | 5-0 | 33-16-12 | D04994J | | 1 | | | | | D07986J | 2 | | | ALL |
| 59X | 22 | | PQ | 5-0 | 33-16-12 | D04994J | | 2 | | | | | D07986J | 3 | | | ALL |
| 59XZ | | | | 0-0 | 33-16-12 | D04994J | | DED | | | | | D07986J | DED | | | ALL |
| 59Y | 22 | | PQ | 4-0 | 33-16-12 | D07988J | | 2 | | | | | TB0104Y | A033 | BJ | | ALL |
| 59YZ | | | | 0-0 | 33-16-12 | D07988J | | DED | | | | | TB0104Y | DED | | | ALL |
| 59Z | 22 | | PQ | 6-0 | 33-16-12 | D04994J | | 6 | | | | | TB0104Y | A033 | BJ | | ALL |
| 59ZZ | | | | 0-0 | 33-16-12 | D04994J | | DED | | | | | TB0104Y | DED | | | ALL |
| 600 | 22 | | PA | 5-0 | 33-22-33 | D07986J | | 28 | | | | | D05124J | 41 | | | 050-099 |
| 600 | 22 | | PA | 6-0 | 33-22-33 | D07986J | | 28 | | | | | D05124J | 41 | | | 162-199 |
| 601 | 18 | | PA | 8-0 | 33-13-16 | D01374 | | 1 | DK | | | | TB0064G | 4 | 2 | | ALL |
| 602 | 18 | | PA | 7-0 | 33-13-16 | D01374 | | 2 | DK | | | | GD00112 | A.. | 2 | | ALL |
| 603 | 22 | | PA | 8-0 | 33-16-17 | TB0066Z | | 27 | BJ | | | | D01374 | 3 | | | ALL |
| 604 | 22 | | PA | 8-0 | 33-16-17 | TB0066Z | | 29 | BJ | | | | D01374 | 4 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 87

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 605 | 22 | | PA | | 14-0 | 28-42-11 | D05764J | | 11 | | D01374 | | 5 | | ALL |
| 606 | 22 | | PA | | 15-0 | 28-42-11 | D05356J | | 16 | | D01374 | | 6 | | ALL |
| 607 | 24 | | PK | | 12-0 | 34-61-24 | D12178 | | 7 | | TB0104X | D026 | BJ | | 050-099, 155-199, 276-299 |
| 609 | 20 | | PA | | 6-0 | 34-61-24 | D12178 | | 8 | | GD00263 | D.. | 2 | | 050-099, 155-199, 276-299 |
| 60B | 22 | | PQ | SH | 14-0 | 33-16-12 | D06158P | | 4 | | TB0066Y | A031 | BJ | | ALL |
| 60BZ | | | | SH | 0-0 | 33-16-12 | D06158P | DED | | | TB0066Y | DED | | | ALL |
| 60C | 22 | | PQ | SI | 9-0 | 33-16-12 | D06158P | | 5 | | TB0104Y | A033 | BJ | | ALL |
| 60CZ | | | | SI | 0-0 | 33-16-12 | D06158P | DED | | | TB0104Y | DED | | | ALL |
| 60D | 22 | | PQ | SJ | 14-0 | 33-16-12 | TB0066Y | C031 | BJ | | D06158P | | 6 | | ALL |
| 60DZ | | | | SJ | 0-0 | 33-16-12 | TB0066Y | DED | | | D06158P | DED | | | ALL |
| 60F | 22 | | PA | | 14-0 | 33-16-12 | D06156P | | 4 | | TB0066Z | 33 | BJ | | ALL |
| 60G | 22 | | PA | | 14-0 | 33-16-12 | D06156P | | 5 | | TB0066Z | 34 | BJ | | ALL |
| 60H | 22 | | PA | | 14-0 | 33-16-17 | D06156P | | 11 | | TB0066Y | A036 | BJ | | ALL |
| 60J | 22 | | PA | | 14-0 | 33-16-17 | D06156P | | 12 | | TB0066Y | C036 | BJ | | ALL |
| 60K | 22 | | PA | | 9-0 | 33-16-22 | D06156P | | 13 | | TB0104Y | A035 | BJ | | ALL |
| 60L | 22 | | PA | | 14-0 | 33-16-22 | D06156P | | 14 | | TB0066Z | 27 | BJ | | ALL |
| 60M | 22 | | PQ | SF | 14-0 | 33-16-22 | D06158P | | 13 | | TB0066Y | A035 | BJ | | ALL |
| 60MZ | | | | SF | 0-0 | 33-16-22 | D06158P | DED | | | TB0066Y | DED | | | ALL |
| 60N | 22 | | PQ | SG | 14-0 | 33-16-22 | D06158P | | 14 | | TB0066Y | C035 | BJ | | ALL |
| 60NZ | | | | SG | 0-0 | 33-16-22 | D06158P | DED | | | TB0066Y | DED | | | ALL |
| 60S | 22 | | PA | | 9-0 | 33-16-22 | D06156P | | 15 | | TB0104Y | C035 | BJ | | ALL |
| 60T | 22 | | PA | | 14-0 | 33-16-22 | D06156P | | 16 | | TB0066Z | 29 | BJ | | ALL |
| 60W | 22 | | PA | | 10-0 | 33-16-22 | TB0104Y | C035 | BJ | | TB0066Z | 28 | BJ | | ALL |
| 610 | 24 | | PK | | 8-0 | 28-22-11 | D05006P | | 37 | | D01374 | | 10 | | ALL |
| 611 | 22 | | PA | | 11-0 | 34-61-15 | TB0104X | C026 | BJ | | D05006P | | 32 | | 050-099 |
| 611 | 22 | | PA | | 13-0 | 34-61-15 | D05006P | | 32 | | TB0104X | C026 | BJ | | 150-154 |
| 611 | 22 | | PA | | 12-0 | 34-61-15 | D05006P | | 32 | | TB0104X | C026 | BJ | | 155-199, 275-299 |
| 612 | 24 | | PK | | 14-0 | 28-22-11 | D01374 | | 12 | | D04286J | | 1 | | ALL |
| 613 | 24 | | PK | | 7-0 | 28-22-12 | D01374 | | 13 | | TB0066Y | A020 | BJ | | 050-099, 155-199, 276-299 |
| 613 | 24 | | PK | | 8-0 | 28-22-12 | D01374 | | 13 | | D05006P | | 38 | | 150-154, 275 |
| 614 | 24 | | PK | | 14-0 | 28-22-12 | D01374 | | 14 | | D04286J | | 12 | | ALL |
| 615 | 22 | | PA | | 15-0 | 28-42-12 | D05356J | | 17 | | D01374 | | 15 | | ALL |
| 618 | 22 | | PA | | 7-0 | 28-42-12 | TB0066Y | C020 | BJ | | D01374 | | 18 | | 050-099, 155-199, 276-299 |
| 618 | 22 | | PA | | 14-0 | 28-42-12 | D05406J | | 7 | | D01374 | | 18 | | 150-154, 275 |
| 61A | 24 | | PK | | 5-0 | 36-11-21 | D07974J | | 2 | | D04870J | | 15 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 88

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 61B | 20 | | PA | 5-0 | 36-11-41 | D07974J | | 3 | | | | | D05356J | 15 | | | ALL |
| 61C | 24 | | PK | 5-0 | 36-11-41 | D07974J | | 4 | | | | | D04870J | 12 | | | ALL |
| 61D | 24 | | PK | 11-0 | 36-11-41 | TB0066X | | | C001 | BJ | | | D04870J | 13 | | | ALL |
| 61E | 18 | | PA | 5-0 | 36-11-52 | D07974J | | 5 | | DL | | | D05764J | 1 | DK | | 050-099, 155-199, 276-299 |
| 61E | 22 | | PA | 5-0 | 36-11-52 | D07974J | | 5 | | | | | D05764J | 1 | | | 150-154, 275 |
| 61F | 24 | | PK | 5-0 | 36-11-52 | D07974J | | 6 | | | | | D05764J | 8 | | | ALL |
| 61G | 22 | | PA | 6-0 | 36-11-52 | D05764J | | 2 | | | | | TB0104X | C004 | BJ | | ALL |
| 61H | 24 | | PK | 5-0 | 36-21-11 | D07974J | | 7 | | | | | D04286J | 26 | | | ALL |
| 61J | 18 | | PA | 6-0 | 36-11-52 | D07974J | | 8 | | DL | | | D04766J | 8 | DK | | 150-154 |
| 61K | 18 | | PA | 5-0 | 38-32-14 | D07974J | | 13 | | DL | | | D04286J | 2 | DK | | ALL |
| 61L | 16 | | PA | 5-0 | 73-21-20 | D04758J | | 40 | | FM | | | D07986J | 41 | FL | | ALL |
| 61M | 24 | | PK | 5-0 | 38-15-11 | D07974J | | 11 | | | | | D04286J | 16 | | | ALL |
| 61N | 18 | | PA | 5-0 | 38-32-11 | D04286J | | 8 | | DK | | | D07974J | 12 | DL | | 050-099, 150-155, 162-165 |
| 61N | 18 | | PA | 5-0 | 38-32-11 | TB0100F | | | A035 | 2 | | | D07974J | 12 | DL | | 156 |
| 61N | 18 | | PA | 6-0 | 38-32-11 | D04870J | | 47 | | DK | | | D07974J | 12 | DL | | 275-276 |
| 61T | 22 | | PA | 6-0 | 23-43-11 | D05006P | | 39 | | | | | TB0066X | A007 | BJ | | ALL |
| 61X | 18 | | PA | 4-0 | 38-32-11 | D07974J | | 12 | | DL | | | TB0100F | A035 | 2 | | 157, 166-199, 277-299 |
| 622 | 22 | | PA | 15-0 | 28-41-13 | D01374 | | 22 | | | | | TB0100Y | A012 | BJ | | ALL |
| 624 | 20 | | PA | 7-0 | 28-22-11 | D01374 | | 24 | | | | | GD00104 | D.. | 2 | | ALL |
| 629 | 24 | | PK | 6-0 | 28-22-12 | D05006P | | 38 | | | | | TB0066Y | A020 | BJ | | 050-099, 155-199, 276-299 |
| 62B | 24 | | PK | 5-0 | 73-21-17 | D07986J | | 16 | | | | | D04758J | 3 | | | ALL |
| 62D | 22 | | PA | 6-0 | 74-31-21 | TB0102Y | | | A026 | BJ | | | D04760J | 3 | | | ALL |
| 62E | 22 | | PA | 6-0 | SPARE | TB0102Y | | | CAP | Y | | | D04760J | 1 | | | ALL |
| 62F | 22 | | PQ | 6-0 | 74-31-21 | TB0104Y | | | A012 | BJ | | | D04754J | 1 | | | ALL |
| 62FZ | | | PA | 0-0 | 74-31-21 | TB0104Y | | | DED | | | | D04754J | DED | | | ALL |
| 62G | 22 | | PQ | 6-0 | 74-31-21 | TB0104Y | | | A012 | BJ | | | D04754J | 3 | | | ALL |
| 62GZ | | | PB | 0-0 | 74-31-21 | TB0104Y | | | DED | | | | D04754J | DED | | | ALL |
| 62H | 22 | | PQ | 6-0 | 74-31-21 | TB0104X | | | C006 | BJ | | | D04754J | 2 | | | ALL |
| 62HZ | | | PC | 0-0 | 74-31-21 | TB0104X | | | DED | | | | D04754J | DED | | | ALL |
| 62J | 24 | | PK | 6-0 | 74-31-21 | TB0104X | | | D006 | BJ | | | D04758J | 48 | | | ALL |
| 62K | 24 | | PK | 5-0 | 75-23-11 | D07986J | | 17 | | | | | D04760J | 18 | | | ALL |
| 62L | 16 | | PA | 5-0 | 73-21-20 | D07986J | | 18 | | FL | | | D04758J | 5 | FM | | 050-099, 150-199 |
| 62L | 16 | | PA | 6-0 | 73-21-20 | D07986J | | 18 | | FL | | | D04758J | 5 | FM | | 275-299 |
| 62R | 20 | | PA | 5-0 | 73-21-19 | D07986J | | 21 | | | | | D04758J | 30 | | | ALL |
| 62W | 24 | | PK | 4-0 | 78-34-21 | D07986J | | 24 | | | | | TB0104Y | C012 | BJ | | ALL |
| 62X | 24 | | PK | 6-0 | 78-34-21 | TB0104Y | | | C012 | BJ | | | D04758J | 4 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 89

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 62Y | 24 | | PK | 6-0 | 78-34-21 | TB0104X | B006 | BJ | | D04758J | 29 | | | ALL | |
| 630 | 24 | | PK | 11-0 | 28-22-12 | D04286J | | 28 | | TB0066Y | A020 | BJ | | 050-099, 155-199, 276-299 | |
| 631 | 20 | | PA | 8-0 | 33-42-21 | D05006P | | 27 | | D00842 | 1 | | | 050-099 | |
| 631 | 18 | | PA | 8-0 | 33-42-21 | D05006P | | 27 | DL | D00842 | 1 | DK | | 150-199, 275-299 | |
| 632 | 20 | | PA | 6-0 | 33-42-21 | D00842 | | 2 | | D04972P | 11 | | | 050-099 | |
| 632 | 18 | | PA | 6-0 | 33-42-21 | D00842 | | 2 | DK | D04972P | 11 | DK | | 150-199, 275-299 | |
| 636 | 22 | | PQ | 14-0 | 28-31-11 | D12176 | | 12 | | D04286J | 10 | | | 050-099, 155-199, 276-299 | |
| 636Z | | | | 0-0 | 28-31-11 | D12176 | | | DED | D04286J | DED | | | 050-099, 155-199, 276-299 | |
| 639 | 22 | | PA | 6-0 | 28-31-11 | TB0102Y | A037 | BJ | | D04286J | 5 | | | 050-099, 155-199, 276-299 | |
| 63A | 24 | | PK | 8-0 | 78-36-21 | D07986J | | 25 | | TB0102Z | 20 | BJ | | ALL | |
| 63B | 24 | | PK | 8-0 | 78-36-21 | TB0102Z | | 20 | BJ | D04758J | 6 | | | ALL | |
| 63C | 22 | | PA | 4-0 | 79-32-11 | D07986J | | 27 | | D04754J | 7 | | | ALL | |
| 63D | 24 | | PK | 8-0 | 78-36-21 | D04760J | | 6 | | TB0102Z | 20 | BJ | | ALL | |
| 63F | 22 | | PA | 5-0 | 31-41-11 | D07988J | | 4 | | D04754J | 11 | | | ALL | |
| 63H | 24 | | PK | 6-0 | 31-41-13 | D04758J | | 55 | | TB0100Z | 21 | BJ | | ALL | |
| 63J | 22 | | PA | 5-0 | 31-41-17 | D07988J | | 5 | | D04754J | 10 | | | ALL | |
| 63K | 24 | | PK | 6-0 | 24-51-71 | TB0100X | A004 | BJ | | D04794J | 6 | | | ALL | |
| 63L | 20 | | PA | 6-0 | 22-21-21 | D05006P | | 36 | | TB0066X | B008 | BJ | | ALL | |
| 63P | 24 | | PK | 6-0 | 21-44-11 | TB0106Y | C014 | BJ | | D05062J | 4 | | | ALL | |
| 63R | 24 | | PK | 5-0 | 52-71-11 | D07974J | | 23 | | D05906J | 19 | | | ALL | |
| 63V | 24 | | PK | 6-0 | 21-58-11 | TB0102X | D001 | BJ | | D04766J | 35 | | | ALL | |
| 63W | 24 | | PK | 6-0 | 21-58-11 | TB0102X | C001 | BJ | | D05416J | 24 | | | ALL | |
| 646 | 24 | | PK | 12-0 | 36-11-41 | TB0064D | C010 | 2 | | D04870J | 45 | | | ALL | |
| 64A | 22 | | PA | 6-0 | 33-11-16 | D05006P | | 19 | | TB0066X | B003 | BJ | | ALL | |
| 64B | 24 | | PK | 4-0 | 27-18-11 | D07976J | | 22 | | TB0100Y | A013 | BJ | | ALL | |
| 64C | 24 | | PK | 5-0 | 27-38-11 | D07976J | | 23 | | D04870J | 31 | | | ALL | |
| 64D | 20 | | PA | 5-0 | 78-34-21 | D07986J | | 12 | | TB0106Y | A028 | BJ | | 050-099 | |
| 64D | 20 | | PA | 6-0 | 78-34-21 | D07986J | | 12 | | TB0106Y | A028 | BJ | | 150-154, 156-199, 275-299 | |
| 64D | 20 | | PA | 6-0 | 78-34-21 | D07986J | | 12 | | TB0106Y | A025 | BJ | | 155 | |
| 64E | 20 | | PQ | 6-0 | 78-34-21 | D04758J | | 54 | | D04754J | 29 | | | 050-099, 150-199, 275-276, 280-299 | |
| 64E | 20 | | PQ | 4-0 | 78-34-21 | D04758J | | 54 | | D04754J | 29 | | | 277-278 | |
| 64EZ | | | | 0-0 | 78-34-21 | D04758J | | | GB | D04754J | 30 | | | 050-099, 150-156, 162-166, 275-276 | |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 90
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|--|----|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | | |
| 64EZ | | | AB | 0-0 | 78-34-21 | D04754J | 30 | | | | | | | | | | GB | 157, 167-199, 277-299 |
| 64F | 20 | PA | | 11-0 | 78-34-21 | GD04442 | S.. | 2 | | | | | | | | | GE | ALL |
| 64H | 20 | PA | | 4-0 | 78-34-21 | D05006P | 35 | | | | | | D.. | 2 | | | | ALL |
| 64L | 22 | PA | | 6-0 | 33-51-11 | TB0106X | D005 | BJ | | | | | 30 | | | | | ALL |
| 64M | 22 | PA | | 6-0 | 33-51-11 | TB0106X | D004 | BJ | | | | | 12 | | | | | ALL |
| 64N | 22 | PA | | 8-0 | 33-16-17 | D07986J | 4 | | | | | | 19 | | | | | ALL |
| 64V | 20 | PA | | 6-0 | 33-21-21 | D07986J | 22 | | | | | | 2 | | | | | ALL |
| 64W | 20 | PA | | 4-0 | 26-16-21 | D07976J | 1 | | | | | | A006 | BJ | | | | ALL |
| 64X | 20 | PA | | 4-0 | 26-16-21 | D07976J | 17 | | | | | | D003 | BJ | | | | ALL |
| 64Y | 18 | PA | | 6-0 | 25-31-11 | TB0102G | 41 | 2 | | | | | 8 | DK | | | | 050-099, 150-199 |
| 64Y | 16 | PA | | 6-0 | 25-31-11 | TB0102G | 41 | 2 | | | | | 8 | FM | | | | 275-299 |
| 64Z | 20 | PA | | 6-0 | 25-31-11 | TB0102G | 41 | 2 | | | | | 40 | | | | | 050-099, 150-199, 275-278 |
| 64Z | 18 | PA | | 6-0 | 25-31-11 | TB0102G | 41 | 2 | | | | | 40 | DK | | | | 280-299 |
| 651 | 22 | PA | | 8-0 | 33-16-17 | D01310 | 1 | | | | | | 27 | BJ | | | | ALL |
| 652 | 22 | PA | | 8-0 | 33-16-17 | D01310 | 2 | | | | | | 29 | BJ | | | | ALL |
| 653 | 22 | PQ | SP | 8-0 | 33-16-17 | D01310 | 3 | | | | | | 14 | BJ | | | | ALL |
| 653Z | | | SP | 0-0 | 33-16-17 | D01310 | DED | | | | | | DED | | | | | ALL |
| 654 | 22 | PQ | SQ | 8-0 | 33-16-17 | D01310 | 4 | | | | | | 16 | BJ | | | | ALL |
| 654Z | | | SQ | 0-0 | 33-16-17 | D01310 | DED | | | | | | DED | | | | | ALL |
| 655 | 24 | PK | | 15-0 | 24-51-23 | D01310 | 5 | | | | | | 33 | | | | | ALL |
| 656 | 16 | PA | | 13-0 | SPARE | D01310 | 6 | FM | | | | | 42 | 2 | | | | 280-299 |
| 657 | 20 | PA | | 8-0 | 25-31-11 | D01310 | 7 | | | | | | 30 | | | | | 050-099, 150-199 |
| 657 | 16 | PA | | 8-0 | 25-31-11 | D01310 | 7 | FM | | | | | 30 | FL | | | | 275-299 |
| 658 | 24 | PK | | 15-0 | 24-51-23 | D01310 | 8 | | | | | | 32 | | | | | ALL |
| 659 | 24 | PK | | 15-0 | 24-22-21 | D01310 | 9 | | | | | | A004 | BJ | | | | ALL |
| 65A | 24 | PV | FA | 8-0 | 80-11-11 | D04650J | 19 | | | | | | 30 | | | | | ALL |
| 65AZ | | | FA | 0-0 | 80-11-11 | D04650J | DED | | | | | | DED | | | | | ALL |
| 65B | 24 | PV | FB | 8-0 | 80-11-21 | D04650J | 20 | | | | | | 31 | | | | | ALL |
| 65BZ | | | FB | 0-0 | 80-11-21 | D04650J | DED | | | | | | DED | | | | | ALL |
| 65D | 16 | PA | | 6-0 | SPARE | TB0102G | 42 | 2 | | | | | 41 | FM | | | | 280-299 |
| 65E | 16 | PA | | 6-0 | SPARE | TB0102G | 42 | 2 | | | | | 7 | FM | | | | 280-299 |
| 65F | 24 | PK | | 6-0 | 21-61-11 | TB0102Y | A035 | BJ | | | | | 15 | | | | | ALL |
| 65H | 16 | PA | | 6-0 | 30-42-11 | D05006P | 23 | | | | | | 4 | | | | | ALL |
| 65X | 18 | PA | | 6-0 | 38-32-11 | D04286J | 8 | DK | | | | | C035 | 2 | | | | 156-157, 166-199, 277-299 |
| 660 | 20 | PA | | 15-0 | 24-22-21 | D01310 | 10 | | | | | | 13 | | | | | ALL |
| 661 | 24 | PK | | 15-0 | 24-22-21 | D01310 | 11 | | | | | | 15 | | | | | ALL |
| 665 | 24 | PK | | 15-0 | 24-27-21 | D01310 | 15 | | | | | | 28 | | | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 91

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | | |
| 666 | 24 | | PK | 15-0 | 24-51-23 | D01310 | | 16 | | | | | D05406J | | 4 | | | ALL |
| 667 | 16 | | PA | 8-0 | SPARE | D01310 | | 17 | FM | | | | D05006P | | 29 | FL | | 280-299 |
| 668 | 20 | | PA | 15-0 | 25-31-11 | D01310 | | 18 | | | | | TB0102G | | 41 | 2 | | 050-099 |
| 668 | 20 | | PA | 13-0 | 25-31-11 | D01310 | | 18 | | | | | TB0102G | | 41 | 2 | | 150-199 |
| 668 | 16 | | PA | 13-0 | 25-31-11 | D01310 | | 18 | FM | | | | TB0102G | | 41 | 2 | | 275-299 |
| 669 | 24 | | PK | 14-0 | 24-51-23 | D01310 | | 19 | | | | | D07974J | | 19 | | | ALL |
| 66C | 24 | | PK | 2-0 | 32-42-12 | TB0102D | | | | C017 | 2 | | TB0102D | | C018 | 2 | | ALL |
| 66K | 22 | | PA | 7-0 | 25-11-21 | D06192P | | 21 | | | | | D05062J | | 1 | | | ALL |
| 66L | 22 | | PA | 7-0 | 25-11-21 | D06192P | | 22 | | | | | D05062J | | 2 | | | ALL |
| 66M | 22 | | PA | 7-0 | 25-11-21 | D06192P | | 23 | | | | | D05062J | | 3 | | | ALL |
| 66N | 24 | | PK | 5-0 | 73-33-11 | D07986J | | 29 | | | | | D04738J | | 3 | | | 050-099 |
| 66N | 24 | | PK | 5-0 | 73-33-11 | D04738J | | 3 | | | | | D07986J | | 29 | | | 150-199, 275-299 |
| 66R | 24 | | PK | 4-0 | 35-11-13 | D07974J | | 38 | | | | | TB0104X | | B007 | BJ | | ALL |
| 66U | 16 | | PA | 7-0 | 28-22-11 | D05920P | | 1 | | | | | D05928J | | 7 | | | ALL |
| 66V | 16 | | PA | 7-0 | 28-22-11 | D05920P | | 2 | | | | | D05928J | | 8 | | | ALL |
| 66W | 16 | | PA | 7-0 | 28-22-11 | D05920P | | 3 | | | | | D05928J | | 9 | | | ALL |
| 66X | 16 | | PA | 5-0 | 28-22-11 | D05920P | | 4 | | | | | D04286J | | 15 | | | 050-099 |
| 66X | 16 | | PA | 6-0 | 28-22-11 | D05920P | | 4 | | | | | D04286J | | 15 | | | 150-199, 275-299 |
| 66Y | 16 | | PA | 5-0 | 28-22-11 | D05920P | | 5 | | | | | D04286J | | 19 | | | 050-099 |
| 66Y | 16 | | PA | 6-0 | 28-22-11 | D05920P | | 5 | | | | | D04286J | | 19 | | | 150-199, 275-299 |
| 66Z | 16 | | PA | 5-0 | 28-22-11 | D05920P | | 6 | | | | | D04286J | | 23 | | | 050-099 |
| 66Z | 16 | | PA | 6-0 | 28-22-11 | D05920P | | 6 | | | | | D04286J | | 23 | | | 150-156, 162-166, 275-276 |
| 670 | 24 | | PK | 15-0 | 24-41-12 | D01310 | | 20 | | | | | TB0096X | | C002 | BJ | | ALL |
| 671 | 20 | | PA | 7-0 | 24-41-12 | D01310 | | 21 | | | | | GD00102 | | D.. | 2 | | ALL |
| 673 | 24 | | PK | 16-0 | 24-22-21 | D01310 | | 23 | | | | | D10114 | | 22 | | | ALL |
| 674 | 20 | | PA | 15-0 | 24-22-21 | D01310 | | 24 | | | | | D04794J | | 12 | | | ALL |
| 676 | 24 | | PK | 15-0 | 24-41-11 | D01310 | | 26 | | | | | TB0096X | | D001 | BJ | | ALL |
| 677 | 24 | | PK | 15-0 | 24-41-11 | D01310 | | 27 | | | | | TB0096X | | C001 | BJ | | ALL |
| 678 | 24 | | PK | 15-0 | 24-11-21 | D01310 | | 28 | | | | | D04794J | | 9 | | | ALL |
| 67A | 12 | | PA | 5-0 | 28-22-12 | D06192P | | 2 | | | | | D06258J | | 1 | | | ALL |
| 67B | 12 | | PA | 5-0 | 28-22-12 | D06192P | | 4 | | | | | D06258J | | 2 | | | ALL |
| 67C | 12 | | PA | 5-0 | 28-22-12 | D06192P | | 6 | | | | | D06258J | | 4 | | | ALL |
| 67D | 24 | | PK | 5-0 | 32-42-12 | D04738J | | 18 | | | | | TB0102D | | C017 | 2 | | ALL |
| 67F | 16 | | PA | 6-0 | 28-22-11 | D05920P | | 6 | | | | | D04286J | | 23 | | | 157, 167-199, 277-299 |
| 681 | 22 | | PQ | 8-0 | 33-16-17 | D01310 | | 31 | | | | | TB0068Y | | A017 | BJ | | ALL |
| 681Z | | | | 0-0 | 33-16-17 | D01310 | | | DED | | | | TB0068Y | | DED | | | ALL |
| 682 | 24 | | PK | 15-0 | 24-22-22 | D01310 | | 32 | | | | | D04794J | | 17 | | | ALL |
| 683 | 20 | | PA | 15-0 | 24-22-22 | D01310 | | 33 | | | | | D04794J | | 18 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 92

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 684 | 24 | | PK | 15-0 | 24-27-21 | D01310 | | 34 | | | | | D04794J | 30 | | | ALL |
| 685 | 24 | | PK | 15-0 | 24-27-21 | D01310 | | 35 | | | | | D04794J | 29 | | | ALL |
| 686 | 24 | | PK | 15-0 | 24-22-22 | D01310 | | 36 | | | | | D04794J | 42 | | | ALL |
| 68D | 22 | | PQ | AL | 14-0 | 73-21-11 | D02085 | | 22 | | | | D06258J | 14 | | | ALL |
| 68DZ | | | | AL | 0-0 | 73-21-11 | D02085 | | | | | FB | D06258J | | | FC | ALL |
| 68E | 22 | | PQ | AJ | 14-0 | 73-21-11 | D02085 | | 21 | | | | D06258J | 5 | | | ALL |
| 68EZ | | | | AJ | 0-0 | 73-21-11 | D02085 | | | | | FB | D06258J | | | FC | ALL |
| 68G | 22 | | PQ | AM | 14-0 | 73-21-11 | D02085 | | 16 | | | | D06258J | 15 | | | ALL |
| 68GZ | | | | AM | 0-0 | 73-21-11 | D02085 | | | | | FB | D06258J | | | FC | ALL |
| 692 | 24 | | PK | | 17-0 | 24-51-43 | D01310 | | 42 | | | | D05846P | 11 | | | ALL |
| 693 | 24 | | PK | | 17-0 | 24-51-43 | D01310 | | 43 | | | | D05846P | 10 | | | ALL |
| 69D | 22 | | PQ | JD | 8-0 | 73-21-11 | TB0066X | A002 | | BJ | | | D02085 | 15 | | | ALL |
| 69DZ | | | | JD | 0-0 | 73-21-11 | TB0066X | B002 | | BJ | | | D02085 | DED | | | 050-099, 162-199, 277-299 |
| 69DZ | | | | JD | 0-0 | 73-21-11 | TB0066X | DED | | | | | D02085 | DED | | | 150-157, 275-276 |
| 700 | 20 | | PA | | 11-0 | 28-31-11 | D05006P | | 13 | | | | TB0102Y | A037 | | BJ | 050-099, 155-199, 276-299 |
| 703 | 22 | | PA | | 7-0 | 33-16-17 | TB0066Y | A031 | | BJ | | | D00878 | 3 | | | ALL |
| 704 | 22 | | PA | | 7-0 | 33-16-17 | TB0066Z | | 34 | BJ | | | D00878 | 4 | | | ALL |
| 705 | 20 | | PA | | 7-0 | 30-41-12 | D00878 | | 5 | | | | GD00104 | A.. | 2 | | ALL |
| 706 | 20 | | PA | | 7-0 | 30-41-12 | D00878 | | 6 | | | | GD00104 | A.. | 2 | | ALL |
| 707 | 20 | | PA | | 12-0 | 28-31-11 | D12178 | | 2 | | | | TB0102Y | A037 | | BJ | 050-099, 155-199, 276-299 |
| 708 | 22 | | PQ | DK | 13-0 | 28-31-12 | D12176 | | 9 | | | | D04286J | 25 | | | 050, 155-199, 277-299 |
| 708 | 22 | | PQ | DK | 20-0 | 28-31-12 | D12176 | | 9 | | | | D04286J | 25 | | | 051-099 |
| 708Z | | | | DK | 0-0 | 28-31-12 | D12176 | DED | | | | | D04286J | DED | | | 050-099, 155-199, 277-299 |
| 710 | 22 | | PA | | 14-0 | 30-41-12 | D00878 | | 10 | | | | TB0102Y | A031 | | BJ | ALL |
| 711 | 22 | | PA | | 14-0 | 30-41-12 | D00878 | | 11 | | | | TB0102Y | C031 | | BJ | ALL |
| 712 | 24 | | PK | | 14-0 | 30-41-12 | D00878 | | 12 | | | | D05356J | 3 | | | ALL |
| 713 | 24 | | PK | | 14-0 | 30-41-12 | D00878 | | 13 | | | | D05356J | 5 | | | ALL |
| 715 | 22 | | PQ | DB | 14-0 | 28-31-12 | D12176 | | 5 | | | | D04286J | 11 | | | 050-099, 155-199, 276-299 |
| 715Z | | | | DB | 0-0 | 28-31-12 | D12176 | DED | | | | | D04286J | DED | | | 050-099, 155-199, 276-299 |
| 71B | 20 | | PA | | 5-0 | 33-21-11 | D07988J | | 8 | | | | D05124J | 1 | | | 050-099 |
| 71G | 20 | | PA | | 6-0 | 33-21-11 | D07988J | | 16 | | | | D05124J | 40 | | | 150-199 |
| 720 | 22 | | PA | | 14-0 | 28-31-21 | D12178 | | 6 | | | | D04286J | 6 | | | 050-099, 155-199, 276-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 93

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 723 | 22 | PQ | DD | | 12-0 | 28-42-12 | TB0070Y | C020 | BJ | | D04286J | 22 | | | 050-099 |
| 723 | 22 | PQ | DD | | 13-0 | 28-42-12 | TB0070Y | C020 | BJ | | D04286J | 22 | | | 155-199, 276-299 |
| 723Z | | | DD | | 0-0 | 28-42-12 | TB0070Y | | | | D04286J | DED | | | 050-099, 155-199, 276-299 |
| 724 | 22 | PQ | DC | | 11-0 | 28-42-12 | TB0066Y | C020 | BJ | | D05406J | 7 | | | 050-099, 155-199, 276-299 |
| 724Z | | | DC | | 0-0 | 28-42-12 | TB0066Y | | | | D05406J | DED | | | 050-099, 155-199, 276-299 |
| 725 | 20 | PA | | | 9-0 | 33-44-11 | D00858 | 5 | | | D05006P | 20 | | | ALL |
| 726 | 20 | PA | | | 5-0 | 33-44-11 | D00858 | 6 | | | D04972P | 12 | | | ALL |
| 727 | 20 | PA | | | 9-0 | 33-41-11 | D00858 | 7 | | | D05006P | 28 | | | 050-099 |
| 727 | 18 | PA | | | 9-0 | 33-41-11 | D00858 | 7 | DK | | D05006P | 28 | DL | | 150-199, 275-299 |
| 728 | 20 | PA | | | 15-0 | 33-41-11 | D00858 | 8 | | | D05124J | 22 | | | 050-099 |
| 728 | 18 | PA | | | 15-0 | 33-41-11 | D00858 | 8 | DK | | D05124J | 22 | DK | | 150-199, 275-299 |
| 729 | 20 | PA | | | 15-0 | 33-41-11 | D00858 | 9 | | | D05124J | 23 | | | 050-099 |
| 729 | 18 | PA | | | 15-0 | 33-41-11 | D00858 | 9 | DK | | D05124J | 23 | DK | | 150-199, 275-299 |
| 72A | 20 | PA | | | 3-0 | 24-32-41 | D07974J | 14 | | | TB0096X | C004 | BJ | | 275-299 |
| 730 | 18 | PA | | | 5-0 | 33-42-11 | D00858 | 10 | DK | | D04972P | 24 | DK | | 050-099 |
| 730 | 16 | PA | | | 5-0 | 33-42-11 | D00858 | 10 | FM | | D04972P | 24 | FM | | 150-199, 275-299 |
| 731 | 18 | PA | | | 8-0 | 33-42-11 | D00858 | 11 | DK | | D05006P | 26 | DL | | 050-099 |
| 731 | 16 | PA | | | 8-0 | 33-42-11 | D00858 | 11 | FM | | D05006P | 26 | FL | | 150-199, 275-299 |
| 734 | 22 | PQ | DE | | 14-0 | 28-42-13 | D12176 | 6 | | | D04286J | 24 | | | 050-099, 155-199, 276-299 |
| 734Z | | | DE | | 0-0 | 28-42-13 | D12176 | | | | D04286J | DED | | | 050-099, 155-199, 276-299 |
| 736 | 20 | PA | | | 15-0 | 33-43-11 | D00858 | 16 | | | D05416J | 29 | | | 050-099 |
| 736 | 18 | PA | | | 15-0 | 33-43-11 | D00858 | 16 | DK | | D05416J | 10 | DK | | 150-199, 275-299 |
| 737 | 20 | PA | | | 9-0 | 33-43-11 | D05006P | 24 | | | D00858 | 17 | | | 050-099 |
| 737 | 18 | PA | | | 9-0 | 33-43-11 | D05006P | 24 | DL | | D00858 | 17 | DK | | 150-199, 275-299 |
| 740 | 20 | PA | | | 14-0 | 28-31-11 | D12178 | 3 | | | D04286J | 7 | | | 050-099, 155-199, 276-299 |
| 741 | 20 | PQ | BS | | 7-0 | 28-31-12 | D12178 | 9 | | | TB0070Y | C022 | BJ | | 050-099, 155-199, 277-299 |
| 741Z | | | BS | | 0-0 | 28-31-12 | D12178 | | | | TB0070Y | DED | | | 050-099, 155-199, 277-299 |
| 742 | 20 | PA | | | 14-0 | 28-31-11 | D12178 | 4 | | | D04286J | 9 | | | 050-099, 155-199, 276-299 |
| 743 | 20 | PA | | | 12-0 | 28-31-12 | D12178 | 10 | | | D07972J | 27 | | | 050-099, 155-199, 276-299 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 94
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 744 | 20 | | PA | 14-0 | 28-31-12 | D12178 | | 11 | | | | | D04286J | 18 | | | 050-099, 155-199, 276-299 |
| 745 | 20 | | PA | 14-0 | 28-31-12 | D12178 | | 12 | | | | | D04286J | 20 | | | 050-099, 155-199, 276-299 |
| 749 | 20 | | PQ | BT | 6-0 | 28-31-12 | D12178 | | 1 | | | | GD00263 | S.. | 2 | | 050-099, 155-199, 277-299 |
| 749Z | | | | BT | 0-0 | 28-31-12 | D12178 | | DED | | | | GD00263 | DED | | | 050-099, 155-199, 277-299 |
| 75H | 22 | | PA | | 3-0 | 21-66-21 | D05906J | | 32 | | | | D05124J | 29 | | | 050-099 |
| 75H | 22 | | PA | | 3-0 | 21-66-21 | D05124J | | 29 | | | | D05906J | 32 | | | 162-199 |
| 75J | 22 | | PA | | 6-0 | 21-66-21 | TB0102Y | A039 | BJ | | | | D05124J | 37 | | | 050-099 |
| 75J | 22 | | PA | | 5-0 | 21-66-21 | D05124J | | 37 | | | | TB0102Y | A039 | BJ | | 162-199 |
| 75K | 22 | | PA | | 3-0 | 21-66-21 | D05906J | | 23 | | | | D05124J | 39 | | | 050-099, 162-199 |
| 75L | 22 | | PA | | 3-0 | 21-66-21 | D05906J | | 24 | | | | D05124J | 21 | | | 050-099, 162-199 |
| 75M | 22 | | PA | | 3-0 | 21-66-21 | D05906J | | 25 | | | | D05124J | 38 | | | 050-099, 162-199 |
| 75N | 22 | | PA | | 3-0 | 21-66-21 | D05906J | | 26 | | | | D05124J | 36 | | | 050-099, 162-199 |
| 75R | 22 | | PA | | 3-0 | 21-66-41 | D05124J | | 12 | | | | D05906J | 30 | | | 050-099 |
| 75R | 22 | | PA | | 3-0 | 21-66-41 | D05906J | | 30 | | | | D05124J | 12 | | | 162-199 |
| 75T | 22 | | PA | | 3-0 | 21-66-41 | D05124J | | 45 | | | | D05906J | 31 | | | 050-099 |
| 75T | 22 | | PA | | 3-0 | 21-66-41 | D05906J | | 31 | | | | D05124J | 45 | | | 162-199 |
| 771 | 22 | | PA | | 6-0 | 24-25-11 | D10224 | | 21 | | | | D07976J | 13 | | | ALL |
| 772 | 20 | | PA | | 7-0 | 28-43-11 | D10224 | | 2 | | | | GD04438 | S.. | 2 | | ALL |
| 773 | 20 | | PA | | 7-0 | 28-43-11 | D10224 | | 3 | | | | GD04438 | D.. | 2 | | ALL |
| 774 | 22 | | PA | | 6-0 | 24-25-11 | D10224 | | 22 | | | | D06442J | 2 | | | ALL |
| 775 | 24 | | PK | | 6-0 | 28-43-11 | D10224 | | 5 | | | | TB0100X | C006 | BJ | | ALL |
| 776 | 22 | | PA | | 6-0 | 24-25-11 | D10224 | | 23 | | | | TB0102X | D002 | BJ | | ALL |
| 777 | 24 | | PK | | 14-0 | 34-46-12 | D10224 | | 7 | | | | TB0066X | B010 | BJ | | ALL |
| 778 | 24 | | PK | | 14-0 | 27-32-21 | D10224 | | 8 | | | | TB0066X | B012 | BJ | | ALL |
| 779 | 24 | | PK | | 14-0 | 27-32-11 | D10224 | | 9 | | | | TB0066X | A012 | BJ | | ALL |
| 780 | 24 | | PK | | 6-0 | 30-41-12 | D10224 | | 10 | | | | D05356J | 7 | | | ALL |
| 781 | 24 | | PK | | 6-0 | 30-31-21 | D10224 | | 11 | | | | D05906J | 21 | | | ALL |
| 782 | 22 | | PQ | ZA | 14-0 | 22-21-11 | D10224 | | 12 | | | | TB0066X | A009 | BJ | | ALL |
| 782Z | | | | ZA | 0-0 | 22-21-11 | D10224 | | DED | | | | TB0066X | DED | | | ALL |
| 783 | 24 | | PK | | 14-0 | 31-51-42 | D10224 | | 13 | | | | TB0066X | B011 | BJ | | ALL |
| 784 | 24 | | PK | | 14-0 | 31-51-41 | D10224 | | 14 | | | | TB0066X | A011 | BJ | | ALL |
| 785 | 22 | | PA | | 6-0 | 24-25-11 | D10224 | | 24 | | | | D06442J | 4 | | | ALL |
| 786 | 22 | | PQ | FE | 6-0 | 24-25-11 | D06442J | | 5 | | | | TB0106Y | A014 | BJ | | ALL |
| 786Z | | | | FE | 0-0 | 24-25-11 | D06442J | | DED | | | | TB0106Y | DED | | | ALL |
| 787 | 22 | | PQ | FF | 6-0 | 24-25-11 | D06442J | | 6 | | | | TB0102X | D006 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 95

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | | | |
| 787Z | | | | FF | 0-0 | 24-25-11 | D06442J | | DED | | | | | TB0102X | DED | | | | ALL |
| 788 | 22 | PA | | | 14-0 | 34-12-12 | D10224 | | 18 | | | | | TB0066X | B009 | BJ | | | ALL |
| 789 | 24 | PK | | | 14-0 | 34-12-22 | D10224 | | 19 | | | | | TB0066X | A010 | BJ | | | ALL |
| 792 | 22 | PA | | | 6-0 | 30-11-11 | D05656J | | 12 | | | | | TB0102X | B005 | BJ | | | ALL |
| 798 | 22 | PA | | | 14-0 | 34-33-31 | D10224 | | CAP | Y | | | | TB0066X | A014 | BJ | | | ALL |
| 799 | 22 | PA | | | 14-0 | 34-33-21 | D10224 | | CAP | Y | | | | TB0066X | B013 | BJ | | | ALL |
| 79A | 20 | PA | | | 5-0 | 30-81-11 | D07972J | | 28 | | | | | D05906J | 2 | | | | 050-099, 155-199 |
| 79A | 20 | PA | | | 6-0 | 30-81-11 | D07972J | | 28 | | | | | D05906J | 2 | | | | 150-154 |
| 79C | 20 | PA | | | 11-0 | 30-81-11 | TB0066X | | C003 | BJ | | | | D05906J | 3 | | | | 050-099, 155-199 |
| 79C | 20 | PA | | | 12-0 | 30-81-11 | TB0066X | | C003 | BJ | | | | D05906J | 3 | | | | 150-154 |
| 79D | 20 | PA | | | 14-0 | SPARE | D00890 | | CAP | Y | | | | D05906J | 6 | | | | 050-099, 155-199 |
| 79E | 20 | PA | | | 7-0 | SPARE | D00890 | | CAP | Y | | | | GD00112 | D.. | 2 | | | 050-099, 155-199 |
| 79F | 20 | PA | | | 15-0 | 73-21-16 | D10220 | | 7 | | | | | D05906J | 7 | | | | 150-154 |
| 79F | 20 | PA | | | 14-0 | 73-21-16 | D10220 | | 7 | | | | | D05906J | 7 | | | | 155-199 |
| 79G | 20 | PA | | | 7-0 | 30-11-11 | D10220 | | 14 | | | | | GD00112 | D.. | 2 | | | 050-099, 155-199 |
| 79G | 20 | PA | | | 8-0 | 30-11-11 | D10220 | | 14 | | | | | GD00112 | D.. | 2 | | | 150-154 |
| 79H | 20 | PA | | | 14-0 | 30-81-11 | D10220 | | 17 | | | | | D05906J | 8 | | | | 050-099, 155-199 |
| 79H | 20 | PA | | | 15-0 | 30-81-11 | D10220 | | 17 | | | | | D05906J | 8 | | | | 150-154 |
| 79J | 20 | PA | | | 14-0 | 30-81-11 | D10220 | | 18 | | | | | D05906J | 9 | | | | 050-099, 155-199 |
| 79J | 20 | PA | | | 15-0 | 30-81-11 | D10220 | | 18 | | | | | D05906J | 9 | | | | 150-154 |
| 79L | 22 | PA | | | 14-0 | 30-11-11 | D10220 | | 9 | | | | | D05906J | 11 | | | | 050-099, 155-199 |
| 79L | 22 | PA | | | 15-0 | 30-11-11 | D10220 | | 9 | | | | | D05906J | 11 | | | | 150-154 |
| 79M | 22 | PA | | | 14-0 | 30-11-11 | D10220 | | 12 | | | | | D05906J | 12 | | | | 050-099, 155-199 |
| 79M | 22 | PA | | | 15-0 | 30-11-11 | D10220 | | 12 | | | | | D05906J | 12 | | | | 150-154 |
| 79N | 22 | PA | | | 14-0 | 30-11-11 | D10220 | | 11 | | | | | D05906J | 13 | | | | 050-099, 155-199 |
| 79N | 22 | PA | | | 15-0 | 30-11-11 | D10220 | | 11 | | | | | D05906J | 13 | | | | 150-154 |
| 79P | 22 | PA | | | 14-0 | 30-11-11 | D10220 | | 20 | | | | | D05906J | 14 | | | | 050-099, 155-199 |
| 79P | 22 | PA | | | 15-0 | 30-11-11 | D10220 | | 20 | | | | | D05906J | 14 | | | | 150-154 |
| 79R | 22 | PA | | | 8-0 | 30-11-11 | D10220 | | 13 | | | | | TB0066Y | A021 | BJ | | | 050-099, 155-199 |
| 79R | 22 | PA | | | 9-0 | 30-11-11 | D10220 | | 13 | | | | | TB0066Y | A021 | BJ | | | 150-154 |
| 79T | 22 | PA | | | 8-0 | 30-11-11 | D10220 | | 19 | | | | | TB0066Y | A021 | BJ | | | 050-099, 155-199 |
| 79T | 22 | PA | | | 9-0 | 30-11-11 | D10220 | | 19 | | | | | TB0066Y | A021 | BJ | | | 150-154 |
| 79V | 22 | PA | | | 11-0 | 30-11-11 | D05906J | | 15 | | | | | TB0066Y | A021 | BJ | | | 050-099, 155-199 |
| 79V | 22 | PA | | | 12-0 | 30-11-11 | D05906J | | 15 | | | | | TB0066Y | A021 | BJ | | | 150-154 |
| 79W | 24 | PK | | | 5-0 | 21-51-11 | D05656J | | 2 | | | | | TB0100X | A001 | BJ | | | 050-099, 155-199 |
| 79W | 24 | PK | | | 6-0 | 21-51-11 | D05656J | | 2 | | | | | TB0100X | A001 | BJ | | | 150-154 |
| 800 | 22 | PA | | | 14-0 | 34-33-11 | D10224 | | CAP | Y | | | | TB0066X | A013 | BJ | | | ALL |
| 801 | 22 | PA | | | 7-0 | 27-13-11 | D10114 | | 1 | | | | | TB0102Y | A033 | BJ | | | ALL |
| 802 | 22 | PA | | | 5-0 | 30-21-11 | D00890 | | 15 | | | | | D04972P | 18 | | | | 050-099, 155-199 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 96

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 802 | 22 | | PA | 6-0 | 30-21-11 | D00890 | | 15 | | | | | D04972P | 18 | | | 150-154 |
| 803 | 22 | | PA | 7-0 | 33-16-26 | TB0104Y | | A035 | BJ | | | | D10114 | 3 | | | ALL |
| 804 | 22 | | PA | 7-0 | 33-16-26 | TB0104Y | | C035 | BJ | | | | D10114 | 4 | | | ALL |
| 805 | 20 | | PA | 7-0 | 27-13-11 | D10114 | | 5 | | | | | D05416J | 1 | | | ALL |
| 806 | 20 | | PA | 7-0 | 27-13-11 | D10114 | | 6 | | | | | D05416J | 2 | | | ALL |
| 807 | 20 | | PA | 7-0 | 27-13-11 | D10114 | | 7 | | | | | D07976J | 10 | | | ALL |
| 80A | 16 | | PA | 5-0 | 73-21-11 | D07976J | | 4 | FL | | | | D04754J | 12 | FM | | 050-099 |
| 80A | 16 | | PA | 6-0 | 73-21-11 | D07976J | | 4 | FL | | | | D04754J | 12 | FM | | 150-199, 275-299 |
| 811 | 22 | | PA | 7-0 | 27-23-11 | D10114 | | 11 | | | | | D05416J | 6 | | | ALL |
| 815 | 20 | | PA | 7-0 | 27-23-11 | D10114 | | 15 | | | | | D05416J | 7 | | | ALL |
| 816 | 20 | | PA | 7-0 | 27-23-11 | D10114 | | 16 | | | | | D05416J | 8 | | | ALL |
| 817 | 20 | | PA | 7-0 | 27-23-11 | D10114 | | 17 | | | | | D07976J | 11 | | | ALL |
| 821 | 24 | | PK | 6-0 | 24-22-21 | D10114 | | 21 | | | | | D04794J | 11 | | | ALL |
| 823 | 24 | | PK | 6-0 | 24-22-21 | D10114 | | 23 | | | | | D04794J | 43 | | | ALL |
| 826 | 22 | | PA | 8-0 | 33-16-17 | D10220 | | 3 | | | | | TB0068Y | A019 | BJ | | 050-099, 150-199 |
| 827 | 22 | | PA | 8-0 | 33-16-17 | D10220 | | 4 | | | | | TB0068Z | 22 | BJ | | 050-099, 150-199 |
| 828 | 22 | | PA | 5-0 | 30-21-11 | D00890 | | 13 | | | | | D04972P | 16 | | | 050-099, 155-199 |
| 828 | 22 | | PA | 6-0 | 30-21-11 | D00890 | | 13 | | | | | D04972P | 16 | | | 150-154 |
| 829 | 24 | | PK | 5-0 | 30-21-11 | D00890 | | 2 | | | | | D04972P | 20 | | | 050-099, 155-199 |
| 829 | 24 | | PK | 6-0 | 30-21-11 | D00890 | | 2 | | | | | D04972P | 20 | | | 150-154 |
| 82A | 18 | | PA | 10-0 | 33-13-21 | D10396 | | 1 | DK | | | | D10398 | 2 | DK | | ALL |
| 82B | 18 | | PA | 8-0 | 33-13-21 | D10396 | | 2 | DK | | | | GD04442 | A.. | 2 | | 050-099 |
| 82B | 18 | | PA | 7-0 | 33-13-21 | D10396 | | 2 | DK | | | | GD04442 | A.. | 2 | | 150-199, 275-299 |
| 82C | 24 | | PK | 6-0 | 33-14-11 | TB0104Y | | A021 | BJ | | | | D04994J | 18 | | | ALL |
| 82D | 24 | | PK | 11-0 | 33-14-11 | D10396 | | 4 | | | | | L00741 | =P | C | | 050-099 |
| 82D | 24 | | PK | 10-0 | 33-14-11 | D10396 | | 4 | | | | | L00741 | =P | C | | 150-199, 275-299 |
| 82E | 24 | | PK | 6-0 | 33-14-11 | D10396 | | 5 | | | | | TB0104Y | A021 | BJ | | 050-099 |
| 82E | 24 | | PK | 7-0 | 33-14-11 | D10396 | | 5 | | | | | TB0104Y | A021 | BJ | | 150-199, 275-299 |
| 82G | 24 | | PK | 9-0 | 33-16-11 | TB0100Y | | C013 | BJ | | | | D06156P | 7 | | | ALL |
| 82N | 20 | | PA | 8-0 | 33-14-11 | L00741 | | =G | C | | | | GD04442 | A.. | 2 | | ALL |
| 830 | 24 | | PK | 5-0 | 30-21-11 | D00890 | | 7 | | | | | D04972P | 7 | | | 050-099, 155-199 |
| 830 | 24 | | PK | 6-0 | 30-21-11 | D00890 | | 7 | | | | | D04972P | 7 | | | 150-154 |
| 832 | 22 | | PA | 5-0 | 30-21-11 | D00890 | | 10 | | | | | D04972P | 6 | | | 050-099, 155-199 |
| 832 | 22 | | PA | 6-0 | 30-21-11 | D00890 | | 10 | | | | | D04972P | 6 | | | 150-154 |
| 841 | 18 | | PA | 8-0 | 33-13-16 | D10220 | | 1 | DK | | | | TB0068H | 6 | 2 | | 050-099, 150-199 |
| 841 | 18 | | PA | 8-0 | 33-13-16 | D00890 | | 1 | DK | | | | TB0068H | 6 | 2 | | 275-299 |
| 842 | 18 | | PA | 8-0 | 33-13-16 | D10220 | | 2 | DK | | | | GD00102 | A.. | 2 | | 050-099, 150-199 |
| 842 | 18 | | PA | 8-0 | 33-13-16 | D00890 | | 2 | DK | | | | GD00102 | A.. | 2 | | 275-299 |
| 843 | 22 | | PQ | 8-0 | 33-16-17 | TB0068Y | | C019 | BJ | | | | D00890 | 3 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 97

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 843Z | | | | FD | 0-0 | 33-16-17 | D00890 | | DED | | | | TB0068Y | DED | | | ALL |
| 844 | 22 | PA | | | 8-0 | 33-16-17 | TB0068Z | 22 | BJ | | | | D00890 | 4 | | | ALL |
| 845 | 22 | PA | | | 8-0 | 30-21-11 | D00890 | 5 | | | | | TB0066Y | A017 | BJ | | 050-099, 155-199 |
| 845 | 22 | PA | | | 9-0 | 30-21-11 | D00890 | 5 | | | | | TB0066Y | A017 | BJ | | 150-154 |
| 845 | 22 | PA | | | 8-0 | 30-21-11 | D00890 | 5 | | | | | D04972P | 6 | | | 275-299 |
| 846 | 22 | PA | | | 5-0 | 30-21-11 | D04972P | 17 | | | | | D00890 | 6 | | | 050-099, 155-199 |
| 846 | 22 | PA | | | 8-0 | 30-21-11 | D04972P | 17 | | | | | D00890 | 6 | | | 150-154 |
| 846 | 22 | PA | | | 8-0 | 30-21-11 | TB0066Y | A017 | BJ | | | | D00890 | 6 | | | 275-299 |
| 847 | 24 | PK | | | 8-0 | 30-21-11 | D00890 | 7 | | | | | TB0066Y | A018 | BJ | | 275-299 |
| 848 | 24 | PK | | | 6-0 | 30-21-11 | D05006P | 31 | | | | | TB0066Y | A018 | BJ | | 050-099, 155-199 |
| 848 | 24 | PK | | | 8-0 | 30-21-11 | D05006P | 31 | | | | | TB0066Y | A018 | BJ | | 150-154 |
| 848 | 24 | PK | | | 8-0 | 30-21-11 | D05006P | 31 | | | | | D00890 | 8 | | | 275-299 |
| 849 | 24 | PK | | | 15-0 | 73-21-16 | D00890 | 13 | | | | | D04758J | 31 | | | 275-299 |
| 850 | 20 | PA | | | 8-0 | 73-21-16 | D00890 | 14 | | | | | GD00102 | D.. | 2 | | 275-299 |
| 851 | 22 | PA | | | 8-0 | 30-21-11 | TB0066Y | A018 | BJ | | | | D00890 | 11 | | | 050-099, 150-199 |
| 851 | 22 | PA | | | 8-0 | 30-21-11 | TB0066Y | A017 | BJ | | | | D00890 | 11 | | | 275-299 |
| 852 | 22 | PA | | | 15-0 | 30-11-11 | D05906J | 16 | | | | | D10220 | 6 | | | 050-099, 155-199 |
| 852 | 22 | PA | | | 16-0 | 30-11-11 | D05906J | 16 | | | | | D10220 | 6 | | | 150-154 |
| 852 | 22 | PA | | | 15-0 | 30-11-11 | D05656J | 8 | | | | | D00890 | 12 | | | 275-299 |
| 853 | 24 | PK | | | 15-0 | 73-21-16 | D10220 | 7 | | | | | D04758J | 38 | | | 050-099 |
| 853 | 24 | PK | | | 15-0 | 73-21-16 | D10220 | 6 | | | | | D04758J | 38 | | | 275-299 |
| 854 | 20 | PA | | | 7-0 | 73-21-16 | D10220 | 5 | | | | | GD00100 | D.. | 2 | | 275-299 |
| 855 | 22 | PA | | | 8-0 | SPARE | TB0066Y | A017 | BJ | | | | D04972P | 5 | | | 050-099 |
| 855 | 22 | PA | | | 6-0 | SPARE | TB0066Y | A017 | BJ | | | | D04972P | 5 | | | 155-199 |
| 855 | 22 | PA | | | 8-0 | 30-21-11 | D00890 | 15 | | | | | D04972P | 5 | | | 275-299 |
| 881 | 22 | PA | | | 15-0 | 30-11-11 | D10220 | 8 | | | | | TB0102Z | 19 | BJ | | 050-099, 150-154 |
| 881 | 22 | PA | | | 13-0 | 30-11-11 | D10220 | 8 | | | | | TB0102Z | 19 | BJ | | 155-199 |
| 881 | 22 | PA | | | 15-0 | 30-11-11 | D10220 | 1 | | | | | TB0102Z | 19 | BJ | | 275-299 |
| 882 | 22 | PA | | | 15-0 | 30-11-11 | D10220 | 15 | | | | | D05656J | 11 | | | 050-099, 150-199 |
| 882 | 22 | PA | | | 15-0 | 30-11-11 | D10220 | 2 | | | | | D05656J | 11 | | | 275-299 |
| 884 | 22 | PA | | | 15-0 | 30-11-11 | D10220 | 10 | | | | | TB0102Z | 19 | BJ | | 275-299 |
| 886 | 22 | PA | | | 15-0 | 30-11-11 | D10220 | 10 | | | | | D05656J | 17 | | | 050-099, 150-199 |
| 886 | 22 | PA | | | 15-0 | 30-11-11 | D10220 | 4 | | | | | D05656J | 17 | | | 275-299 |
| 889 | 24 | PV | | SV | 15-0 | 21-51-11 | D10220 | 9 | | | | | TB0100X | A001 | BJ | | 275-299 |
| 889Z | | | | SV | 0-0 | 21-51-11 | D10220 | | DED | | | | TB0100X | DED | | | 275-299 |
| 890 | 22 | PA | | | 11-0 | 30-21-11 | D04766J | 13 | | | | | TB0066Y | A017 | BJ | | 050-099, 155-199 |
| 890 | 22 | PA | | | 12-0 | 30-21-11 | D04766J | 13 | | | | | TB0066Y | A017 | BJ | | 150-154 |
| 891 | 20 | PA | | | 8-0 | 21-51-11 | D10220 | 11 | | | | | GD00102 | D.. | 2 | | 275-299 |
| 90A | 24 | PK | | | 12-0 | 21-61-81 | D13584 | 8 | | | | | TB0102X | C007 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 98

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|--------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0066 | 286T0066 | | | P5 & P61-R2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 90A | 24 | | PK | 14-0 | 21-61-81 | D13584 | | 8 | | | | TB0102X | C007 | BJ | | 150-199 |
| 90A | 24 | | PK | 13-0 | 21-61-81 | D13584 | | 8 | | | | TB0102X | C007 | BJ | | 275-299 |
| 90B | 22 | | PA | 12-0 | 21-61-81 | D13584 | | 7 | | | | TB0102X | D007 | BJ | | 050-099 |
| 90B | 22 | | PA | 14-0 | 21-61-81 | D13584 | | 7 | | | | TB0102X | D007 | BJ | | 150-199 |
| 90B | 22 | | PA | 13-0 | 21-61-81 | D13584 | | 7 | | | | TB0102X | D007 | BJ | | 275-299 |
| 90C | 20 | | PA | 6-0 | 21-61-81 | D13584 | | 6 | | | | GD00112 | D.. | 2 | | ALL |
| 90D | 24 | | PK | 7-0 | 21-61-81 | D13584 | | 5 | | | | TB0070X | A004 | BJ | | ALL |
| FRC | | | | 0-0 | 73-21-11 | D06258J | | | | | FC | D06258J | | 16 | | ALL |
| GRB | | | | 0-0 | 78-34-21 | D04758J | | | | | GB | D04758J | | 16 | | ALL |
| GRE | | | | 0-0 | 78-34-21 | TB0104X | | | | | GE | TB0104X | D009 | BJ | | ALL |
| W0069 | 286T0069 | | | PRE-RECORDED ANNC.T. PNL- FWD CLOSET- JUMPER BUNDLE | | | | | | | | | | | | |
| 001 | 24 | | PK | 3-0 | 23-31-12 | D02567 | | 1 | | | | D06103P | | 1 | | 275-278 |
| 001 | 24 | | PV | AA | 3-0 | 23-31-12 | D02567 | | 1 | | | D06103P | | 1 | | 280-299 |
| 001Z | | | | AA | 0-0 | 23-31-12 | D02567 | | DED | | | D06103P | | DED | | 280-299 |
| 003 | 24 | | PK | | 3-0 | 23-31-12 | D02567 | | 3 | | | D06103P | | 3 | | 275-278 |
| 003 | 24 | | PV | AC | 3-0 | 23-31-12 | D02567 | | 3 | | | D06103P | | 3 | | 280-299 |
| 003Z | | | | AC | 0-0 | 23-31-12 | D02567 | | DED | | | D06103P | | DED | | 280-299 |
| 005 | 22 | | PA | | 3-0 | 23-31-12 | D02567 | | 5 | | | D06103P | | 5 | | 275-278 |
| 005 | 20 | | PA | | 3-0 | 23-31-12 | D02567 | | 5 | | | D06103P | | 5 | | 280-299 |
| 012 | 24 | | PK | | 3-0 | 23-31-12 | D02567 | | 12 | | | D06103P | | 12 | | 275-278 |
| 012 | 24 | | PV | AL | 3-0 | 23-31-12 | D02567 | | 12 | | | D06103P | | 12 | | 280-299 |
| 012Z | | | | AL | 0-0 | 23-31-12 | D02567 | | DED | | | D06103P | | DED | | 280-299 |
| 014 | 24 | | PK | | 3-0 | 23-31-12 | D02567 | | 14 | | | D06103P | | 14 | | 275-278 |
| 014 | 24 | | PV | AN | 3-0 | 23-31-12 | D02567 | | 14 | | | D06103P | | 14 | | 280-299 |
| 014Z | | | | AN | 0-0 | 23-31-12 | D02567 | | DED | | | D06103P | | DED | | 280-299 |
| 020 | 22 | | PA | | 3-0 | 23-31-12 | D02567 | | 20 | | | D06103P | | 20 | | 275-299 |
| 021 | 22 | | PA | | 3-0 | 23-31-12 | D02567 | | 21 | | | D06103P | | 21 | | 275-278 |
| 021 | 20 | | PA | | 3-0 | 23-31-12 | D02567 | | 21 | | | D06103P | | 21 | | 280-299 |
| 023 | 22 | | PA | | 3-0 | 23-31-12 | D02567 | | 23 | | | D06103P | | 23 | | 275-278 |
| 023 | 20 | | PA | | 3-0 | 23-31-12 | D02567 | | 23 | | | D06103P | | 23 | | 280-299 |
| 024 | 24 | | PK | | 3-0 | 23-31-12 | D02567 | | 24 | | | D06103P | | 24 | | 275-278 |
| 024 | 24 | | PV | AX | 3-0 | 23-31-12 | D02567 | | 24 | | | D06103P | | 24 | | 280-299 |
| 024Z | | | | AX | 0-0 | 23-31-12 | D02567 | | DED | | | D06103P | | DED | | 280-299 |
| 201B | 24 | | PW | IA | 3-0 | 23-31-12 | D02567 | | 18 | | | D06103P | | 18 | | 275-299 |
| 201R | 24 | | PW | IA | 0-0 | 23-31-12 | D02567 | | 7 | | | D06103P | | 7 | | 275-299 |
| 201Z | | | | IA | 0-0 | 23-31-12 | D02567 | | DED | | | D06103P | | 22 | | 275-299 |
| 202B | 24 | | PW | IB | 3-0 | 23-31-12 | D02567 | | 17 | | | D06103P | | 17 | | 275-299 |
| 202R | 24 | | PW | IB | 0-0 | 23-31-12 | D02567 | | 6 | | | D06103P | | 6 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0060

Page 99

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|---|-------|----------|-------------|------|------|-----------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0069 | 286T0069 | | | PRE-RECORDED ANNCT. PNL- FWD CLOSET- JUMPER BUNDLE (continued) | | | | | | | | | | | |
| 202Z | | | | IB | 0-0 | 23-31-12 | D02567 | DED | | | D06103P | 19 | | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0060
Page 100 End
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL | | | | | | | | | | | |
| 003 | 22 | | PA | | 8-0 | 33-16-17 | TB0068Z | 13 | BJ | | D01406 | 3 | | | ALL |
| 004 | 22 | | PA | | 8-0 | 33-16-17 | TB0068Z | 16 | BJ | | D01406 | 4 | | | ALL |
| 005 | 22 | | PA | | 8-0 | 29-11-32 | D01406 | 5 | | | D05012P | 1 | | | ALL |
| 006 | 22 | | PA | | 13-0 | 29-32-11 | D01406 | 6 | | | TB0106Y | A018 | BJ | | ALL |
| 008 | 22 | | PA | | 15-0 | 29-11-32 | D01406 | 8 | | | D04938J | 14 | | | ALL |
| 009 | 22 | | PA | | 15-0 | 29-11-32 | D01406 | 9 | | | D04854J | 26 | | | 050-099 |
| 009 | 22 | | PA | | 16-0 | 29-11-32 | D01406 | 9 | | | D04854J | 26 | | | 150-199, 275-299 |
| 010 | 22 | | PA | | 15-0 | 29-11-32 | D01406 | 10 | | | D04854J | 22 | | | 050-099 |
| 010 | 22 | | PA | | 16-0 | 29-11-32 | D01406 | 10 | | | D04854J | 22 | | | 150-199, 275-299 |
| 011 | 22 | | PA | | 15-0 | 29-11-32 | D01406 | 13 | | | D05410J | 18 | | | ALL |
| 015 | 24 | | PK | | 15-0 | 22-41-11 | D01406 | 15 | | | D04541J | 5 | | | ALL |
| 017 | 24 | | PK | | 16-0 | 29-11-32 | D01406 | 17 | | | D04854J | 7 | | | ALL |
| 018 | 22 | | PA | | 16-0 | 33-16-12 | D06160P | 48 | | | TB0070Y | A032 | BJ | | ALL |
| 019 | 22 | | PA | | 16-0 | 33-16-12 | D06160P | 49 | | | TB0070Y | C032 | BJ | | ALL |
| 01A | 24 | | PK | | 6-0 | 21-25-11 | D05042J | 45 | | | TB0098Y | A014 | BJ | | ALL |
| 01B | 24 | | PK | | 6-0 | 21-25-11 | D04952J | 54 | | | TB0098Y | A014 | BJ | | ALL |
| 01C | 24 | | PK | | 7-0 | 21-43-11 | TB0104Y | A014 | BJ | | D05042J | 42 | | | ALL |
| 01D | 24 | | PK | | 7-0 | 21-43-11 | TB0104X | B003 | BJ | | D05042J | 43 | | | ALL |
| 01F | 24 | | PK | | 12-0 | 21-44-11 | TB0066Y | A015 | BJ | | D04952J | 22 | | | ALL |
| 01G | 24 | | PK | | 7-0 | 21-44-11 | TB0106Y | C014 | BJ | | D04952J | 9 | | | ALL |
| 01H | 24 | | PK | | 15-0 | 21-58-11 | D04010P | 16 | | | TB0066Z | 23 | BJ | | ALL |
| 01J | 20 | | PA | | 8-0 | 24-11-11 | D04006P | 5 | | | D04774J | 12 | | | ALL |
| 01K | 20 | | PA | | 8-0 | 24-11-21 | D04008P | 5 | | | D04756J | 12 | | | ALL |
| 01L | 24 | | PK | | 6-0 | SPARE | D04852J | CAP | Y | | TB0098X | CAP | Y | | 051-099, 150-154 |
| 01L | 24 | | PK | | 6-0 | 21-44-21 | D04852J | 24 | | | TB0098X | D008 | BJ | | 275-276 |
| 01M | 24 | | PK | | 6-0 | 24-22-21 | TB0104X | B004 | BJ | | D04952J | 45 | | | ALL |
| 01N | 24 | | PK | | 6-0 | 24-22-21 | TB0104X | A004 | BJ | | D04952J | 44 | | | ALL |
| 01P | 24 | | PK | | 6-0 | 24-22-41 | TB0096X | C010 | BJ | | D04952J | 24 | | | ALL |
| 01R | 24 | | PK | | 6-0 | 24-22-41 | TB0096X | B010 | BJ | | D04952J | 25 | | | ALL |
| 01S | 20 | | PA | | 10-0 | 24-22-41 | TB0096X | A010 | BJ | | D04006P | 11 | | | ALL |
| 01T | 24 | | PK | | 6-0 | 24-28-11 | D04008P | 11 | | | D05410J | 9 | | | ALL |
| 01U | 24 | | PK | | 8-0 | 24-31-11 | D04774J | 20 | | | D04008P | 13 | | | ALL |
| 01V | 24 | | PK | | 7-0 | 24-31-11 | D04774J | 21 | | | TB0106Y | A026 | BJ | | ALL |
| 01W | 24 | | PK | | 10-0 | 24-31-11 | D04008P | 14 | | | TB0106Y | A026 | BJ | | ALL |
| 01X | 24 | | PK | | 7-0 | SPARE | D04852J | CAP | Y | | TB0106Y | CAP | Y | | 051-099, 150-154 |
| 01X | 24 | | PK | | 7-0 | 21-44-21 | D04852J | 26 | | | TB0106Y | C014 | BJ | | 275-276 |
| 01Y | 24 | | PK | | 10-0 | 24-32-11 | D04006P | 13 | | | TB0106X | A001 | BJ | | ALL |
| 01Z | 24 | | PK | | 10-0 | 24-32-11 | D04006P | 14 | | | TB0106X | B001 | BJ | | ALL |
| 020 | 22 | | PA | | 13-0 | 29-11-32 | D01406 | 20 | | | TB0106Y | A019 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 1

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 022 | 22 | PQ | AZ | | 11-0 | 28-22-31 | D01384 | 10 | | | D05010P | 1 | | | ALL |
| 022Z | | | AZ | | 0-0 | 28-22-31 | D01384 | DED | | | D05010P | DED | | | ALL |
| 024 | 22 | PQ | TN | | 13-0 | 29-33-11 | TB0098Y | C011 | BJ | | D01406 | 24 | | | ALL |
| 024Z | | | TN | | 0-0 | 29-33-11 | TB0098Y | DED | | | D01406 | DED | | | ALL |
| 02A | 24 | PK | | | 10-0 | 24-33-11 | D07984J | 23 | | | D04006P | 17 | | | ALL |
| 02B | 24 | PK | | | 10-0 | 24-33-11 | D07984J | 24 | | | D04006P | 16 | | | ALL |
| 02C | 24 | PK | | | 10-0 | 24-33-11 | TB0106Y | C026 | BJ | | D04006P | 18 | | | ALL |
| 02D | 24 | PK | | | 7-0 | 24-33-11 | TB0106Y | C026 | BJ | | D05410J | 11 | | | ALL |
| 02E | 24 | PK | | | 6-0 | 24-34-11 | D04008P | 16 | | | D05410J | 33 | | | ALL |
| 02F | 22 | PA | | | 10-0 | 24-25-11 | D04008P | 17 | | | TB0106Y | A014 | BJ | | ALL |
| 02G | 24 | PK | | | 6-0 | 24-34-11 | D04008P | 18 | | | D05410J | 31 | | | ALL |
| 02H | 24 | PK | | | 6-0 | 24-34-11 | D04008P | 19 | | | D05410J | 34 | | | ALL |
| 02J | 24 | PK | | | 6-0 | 24-34-11 | D04008P | 26 | | | D05410J | 28 | | | ALL |
| 02K | 24 | PK | | | 6-0 | 24-34-11 | D04008P | 27 | | | D05410J | 29 | | | ALL |
| 02L | 24 | PK | | | 6-0 | 24-34-11 | D04008P | 28 | | | D05410J | 30 | | | ALL |
| 02M | 20 | PA | | | 10-0 | 24-41-11 | D04006P | 24 | | | TB0096X | D009 | BJ | | ALL |
| 02N | 24 | PK | | | 10-0 | 24-41-11 | D04006P | 25 | | | TB0096X | D010 | BJ | | ALL |
| 02P | 24 | PK | | | 10-0 | 24-51-31 | D04008P | 9 | | | TB0106Y | A011 | BJ | | ALL |
| 02R | 24 | PK | | | 10-0 | 24-51-31 | D04006P | 9 | | | TB0106Y | C011 | BJ | | ALL |
| 02S | 24 | PK | | | 6-0 | 27-51-61 | D07984J | 14 | | | D04756J | 17 | | | ALL |
| 02T | 24 | PK | | | 6-0 | 27-51-61 | D07984J | 15 | | | D04756J | 18 | | | ALL |
| 02U | 24 | PK | | | 6-0 | 27-88-11 | D07984J | 12 | | | D04774J | 29 | | | ALL |
| 02V | 24 | PK | | | 6-0 | 21-58-16 | D07984J | 31 | | | D08054J | 3 | | | ALL |
| 02W | 24 | PK | | | 10-0 | 24-33-11 | D04006P | 12 | | | TB0106Y | C026 | BJ | | ALL |
| 032 | 24 | PV | FI | | 8-0 | 49-72-11 | D06160P | 46 | | | TB0096X | A004 | BJ | | ALL |
| 032Z | | | FI | | 0-0 | 49-72-11 | D06160P | DED | | | TB0096X | DED | | | ALL |
| 033 | 24 | PV | FH | | 8-0 | 49-72-11 | D06160P | 45 | | | TB0096X | B004 | BJ | | ALL |
| 033Z | | | FH | | 0-0 | 49-72-11 | D06160P | DED | | | TB0096X | DED | | | ALL |
| 03A | 18 | PA | | | 6-0 | 28-21-11 | D04854J | 10 | | | D04010P | 4 | | | ALL |
| 03C | 22 | PA | | | 6-0 | 28-22-21 | D04952J | 49 | | | D04008P | 3 | | | ALL |
| 03D | 22 | PA | | | 4-0 | 28-22-21 | D04952J | 50 | | | D04756J | 14 | | | ALL |
| 03E | 22 | PQ | SR | | 6-0 | 28-22-21 | D05042J | 37 | | | D04006P | 3 | | | ALL |
| 03EZ | | | SR | | 0-0 | 28-22-21 | D05042J | DED | | | D04006P | DED | | | ALL |
| 03F | 22 | PQ | TT | | 4-0 | 28-22-21 | D05042J | 38 | | | D04774J | 13 | | | ALL |
| 03FZ | | | TT | | 0-0 | 28-22-21 | D05042J | DED | | | D04774J | DED | | | ALL |
| 03G | 16 | PA | | | 6-0 | 28-25-11 | D07980J | 11 | FL | | D04854J | 1 | | | ALL |
| 03H | 22 | PA | | | 6-0 | 28-25-11 | D07980J | 12 | | | D05042J | 20 | | | 050-099 |
| 03H | 20 | PA | | | 6-0 | 28-25-11 | D07980J | 12 | | | D05042J | 20 | | | 150-199, 275-299 |
| 03J | 22 | PQ | TS | | 6-0 | 28-25-21 | D04952J | 23 | | | D04010P | 9 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 2

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 03J | 20 | PQ | TS | | 6-0 | 28-25-21 | D04952J | | 23 | | | D04010P | | 9 | | 150-199, 275-299 |
| 03JZ | | | TS | | 0-0 | 28-25-21 | D04952J | | DED | | | D04010P | | DED | | ALL |
| 03K | 18 | PA | | | 6-0 | 28-26-11 | D04854J | | 2 | | | D04010P | | 10 | | ALL |
| 03M | 20 | PA | | | 6-0 | 28-21-13 | D04854J | | 17 | | | D04010P | | 7 | | ALL |
| 03N | 18 | PA | | | 6-0 | 28-41-12 | D04854J | | 8 | | | D04010P | | 8 | | ALL |
| 03P | 22 | PQ | TX | | 6-0 | 29-11-11 | D05042J | | 33 | | | TB0098Y | | C013 | BJ | ALL |
| 03PZ | | | TX | | 0-0 | 29-11-11 | D05042J | | DED | | | TB0098Y | | DED | | ALL |
| 03R | 22 | PQ | TW | | 6-0 | 29-11-11 | D05042J | | 34 | | | TB0098Y | | A013 | BJ | ALL |
| 03RZ | | | TW | | 0-0 | 29-11-11 | D05042J | | DED | | | TB0098Y | | DED | | ALL |
| 03S | 22 | PA | | | 6-0 | 29-11-11 | D07980J | | 15 | | | D05042J | | 32 | | ALL |
| 03T | 22 | PQ | TV | | 7-0 | 29-11-21 | TB0104Y | | A013 | BJ | | D04952J | | 47 | | ALL |
| 03TZ | | | TV | | 0-0 | 29-11-21 | TB0104Y | | DED | | | D04952J | | DED | | ALL |
| 03U | 22 | PQ | TU | | 7-0 | 29-11-21 | TB0104Y | | C013 | BJ | | D04952J | | 48 | | ALL |
| 03UZ | | | TU | | 0-0 | 29-11-21 | TB0104Y | | DED | | | D04952J | | DED | | ALL |
| 03V | 22 | PA | | | 6-0 | 29-11-21 | D07982J | | 15 | | | D04952J | | 46 | | ALL |
| 03W | 22 | PA | | | 7-0 | 29-11-32 | D04854J | | 19 | | | TB0106Y | | A019 | BJ | ALL |
| 03X | 22 | PA | | | 7-0 | 29-11-32 | D04854J | | 15 | | | TB0106Y | | A019 | BJ | ALL |
| 03Y | 22 | PA | | | 16-0 | 29-11-32 | D04854J | | 23 | | | D01406 | | 14 | | ALL |
| 041 | 20 | PA | | | 7-0 | 21-31-11 | D01408 | | 1 | | | GD00110 | | D.. | 2 | ALL |
| 042 | 20 | PA | | | 15-0 | 21-31-31 | D01408 | | 2 | | | D08054J | | 2 | | ALL |
| 043 | 20 | PA | | | 15-0 | 21-31-31 | D01408 | | 3 | | | D08054J | | 1 | | ALL |
| 045 | 22 | PA | | | 13-0 | 33-51-11 | D05010P | | 7 | | | TB0104X | | C007 | BJ | ALL |
| 048 | 20 | PA | | | 8-0 | 21-31-31 | D01408 | | 8 | | | D05012P | | 7 | | ALL |
| 049 | 20 | PA | | | 1-0 | 21-31-31 | D01408 | | 10 | | | D01408 | | 9 | | ALL |
| 04A | 22 | PA | | | 16-0 | 29-11-32 | D01406 | | 31 | | | D04854J | | 32 | | ALL |
| 04B | 24 | PK | | | 6-0 | 29-21-31 | D04010P | | 25 | | | D05042J | | 8 | | ALL |
| 04C | 20 | PA | | | 7-0 | 29-11-32 | D01406 | | 30 | | | GD00267 | | D.. | 2 | ALL |
| 04H | 22 | PA | | | 7-0 | 29-32-11 | D04938J | | 13 | | | TB0106Y | | A018 | BJ | ALL |
| 04J | 22 | PA | | | 7-0 | 29-32-11 | D05410J | | 7 | | | TB0106Y | | A018 | BJ | ALL |
| 04M | 24 | PK | | | 7-0 | 32-09-11 | D07984J | | 18 | | | D04774J | | 54 | | ALL |
| 04N | 12 | PA | | | 7-0 | 32-35-11 | D04010P | | 6 | | | D04986J | | 20 | | ALL |
| 04S | 22 | PA | | | 4-0 | 32-41-11 | D05792J | | 13 | | | D04854J | | 3 | | ALL |
| 04T | 24 | PK | | | 6-0 | 32-42-11 | D07984J | | 21 | | | D04772J | | 2 | | ALL |
| 04U | 24 | PK | | | 6-0 | 32-42-11 | D07984J | | 22 | | | D04772J | | 1 | | ALL |
| 04V | 22 | PA | | | 7-0 | 32-42-11 | TB0106Y | | C017 | BJ | | D05410J | | 8 | | ALL |
| 04W | 22 | PA | | | 7-0 | 32-42-11 | TB0106Y | | C017 | BJ | | D04938J | | 28 | | ALL |
| 04X | 22 | PA | | | 8-0 | 32-44-11 | D04010P | | 14 | | | D04774J | | 3 | | ALL |
| 05A | 24 | PK | | | 9-0 | 33-11-11 | D07982J | | 25 | | | D06160P | | 1 | | ALL |
| 05C | 24 | PK | | | 6-0 | 27-58-21 | D07984J | | 19 | | | D04774J | | 8 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 3

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|---------|-------|------|------|--------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 05D | 24 | | PK | | 7-0 | 33-11-13 | TB0098X | A008 | BJ | | D05792J | 11 | | | ALL |
| 05F | 16 | | PA | | 9-0 | 33-11-14 | TB0096G | 21 | 2 | | D06160P | 4 | FM | | ALL |
| 05G | 16 | | PA | | 7-0 | 33-11-14 | TB0096G | 21 | 2 | | D04986J | 18 | | | ALL |
| 05H | 16 | | PA | | 7-0 | 33-11-14 | TB0096G | 21 | 2 | | D04986J | 16 | | | ALL |
| 05J | 24 | | PK | | 6-0 | 33-13-11 | D07982J | 30 | | | D05784J | 8 | | | ALL |
| 05K | 24 | | PK | | 8-0 | 33-16-11 | D07980J | 29 | | | D06160P | 6 | | | ALL |
| 05M | 22 | | PA | | 6-0 | 33-16-12 | D07980J | 21 | | | D05784J | 1 | | | ALL |
| 05N | 22 | | PQ | SK | 6-0 | 33-16-12 | D07980J | 22 | | | D05784J | 2 | | | ALL |
| 05NZ | | | | SK | 0-0 | 33-16-12 | D07980J | DED | | | D05784J | DED | | | ALL |
| 05P | 22 | | PQ | SL | 6-0 | 33-16-12 | D07982J | 21 | | | D05792J | 1 | | | ALL |
| 05PZ | | | | SL | 0-0 | 33-16-12 | D07982J | DED | | | D05792J | DED | | | ALL |
| 05R | 22 | | PQ | SM | 16-0 | 33-16-12 | D06162P | 8 | | | TB0068Y | A019 | BJ | | ALL |
| 05RZ | | | | SM | 0-0 | 33-16-12 | D06162P | DED | | | TB0068Y | DED | | | ALL |
| 05S | 22 | | PQ | SN | 16-0 | 33-16-12 | D06162P | 9 | | | TB0068Y | C020 | BJ | | ALL |
| 05SZ | | | | SN | 0-0 | 33-16-12 | D06162P | DED | | | TB0068Y | DED | | | ALL |
| 05T | 22 | | PA | | 16-0 | 33-16-12 | D06160P | 8 | | | TB0068Y | C019 | BJ | | ALL |
| 05U | 22 | | PA | | 16-0 | 33-16-12 | D06160P | 9 | | | TB0068Z | 21 | BJ | | ALL |
| 05V | 22 | | PA | | 16-0 | 33-16-12 | D06160P | 10 | | | TB0068Z | 22 | BJ | | ALL |
| 05W | 22 | | PA | | 16-0 | 33-16-17 | D06160P | 11 | | | TB0068Y | A018 | BJ | | ALL |
| 05X | 22 | | PQ | RR | 16-0 | 33-16-17 | D06160P | 12 | | | TB0068Y | C018 | BJ | | ALL |
| 05XZ | | | | RR | 0-0 | 33-16-17 | D06160P | DED | | | TB0068Y | DED | | | ALL |
| 05Y | 22 | | PQ | RS | 8-0 | 33-16-17 | D07982J | 24 | | | D06160P | 19 | | | ALL |
| 05YZ | | | | RS | 0-0 | 33-16-17 | D07982J | DED | | | D06160P | DED | | | ALL |
| 05Z | 22 | | PA | | 2-0 | 33-16-12 | TB0068Y | A020 | BJ | | TB0068Y | C020 | BJ | | ALL |
| 061 | 18 | | PA | | 9-0 | 33-13-16 | D01776 | 1 | DK | | TB0064G | 5 | 2 | | ALL |
| 062 | 18 | | PA | | 7-0 | 33-13-16 | D01776 | 2 | DK | | GD00110 | A.. | 2 | | ALL |
| 063 | 24 | | PK | | 8-0 | 21-33-21 | D01776 | 3 | | | D05012P | 8 | | | ALL |
| 064 | 20 | | PA | | 8-0 | 21-33-21 | D01776 | 4 | | | GD00265 | A.. | 2 | | ALL |
| 06A | 22 | | PQ | SJ | 16-0 | 33-16-22 | D06162P | 13 | | | TB0068Y | A017 | BJ | | ALL |
| 06AZ | | | | SJ | 0-0 | 33-16-22 | D06162P | DED | | | TB0068Y | DED | | | ALL |
| 06C | 22 | | PQ | FO | 16-0 | 33-16-22 | D06162P | 17 | | | TB0068G | 8 | 2 | | ALL |
| 06CZ | | | | FO | 0-0 | 33-16-22 | D06162P | DED | | | TB0068G | DED | | | ALL |
| 06E | 22 | | PA | | 16-0 | 33-16-22 | D06160P | 13 | | | TB0068Z | 13 | BJ | | ALL |
| 06F | 22 | | PA | | 9-0 | 33-16-22 | D06160P | 14 | | | TB0106Z | 37 | BJ | | ALL |
| 06G | 22 | | PA | | 6-0 | 33-16-22 | D06160P | 15 | | | D04756J | 20 | | | ALL |
| 06H | 22 | | PA | | 16-0 | 33-16-22 | D06160P | 16 | | | TB0068Z | 14 | BJ | | ALL |
| 06J | 22 | | PA | | 9-0 | 33-16-22 | D06160P | 17 | | | TB0106Z | 38 | BJ | | ALL |
| 06K | 22 | | PA | | 16-0 | 33-16-22 | D06160P | 18 | | | TB0068Z | 16 | BJ | | ALL |
| 06L | 22 | | PA | | 12-0 | 33-16-22 | TB0106Z | 37 | BJ | | TB0068Y | C017 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0070
 Page 4
 Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | |
| 06M | 22 | | PA | 12-0 | 33-16-22 | TB0106Z | 38 | BJ | | TB0068Z | 15 | BJ | | ALL | | |
| 06S | 24 | | PK | 6-0 | 35-11-13 | TB0104X | | B007 | BJ | D04772J | 7 | | | ALL | | |
| 06U | 22 | | PA | 8-0 | 36-11-51 | TB0098X | | C004 | BJ | D06162P | 20 | | | ALL | | |
| 06V | 24 | | PK | 8-0 | 36-11-51 | TB0098X | | D004 | BJ | D05042J | 48 | | | ALL | | |
| 06W | 22 | | PA | 8-0 | 36-11-52 | TB0104X | | C004 | BJ | D06160P | 20 | | | ALL | | |
| 06X | 24 | | PK | 7-0 | 36-11-52 | TB0104X | | D004 | BJ | D04952J | 8 | | | ALL | | |
| 07A | 16 | | PA | 14-0 | 49-61-11 | D05012P | | 16 | FL | D04952J | 27 | FM | | ALL | | |
| 07B | 22 | | PQ | 7-0 | 49-61-11 | D04952J | | 17 | | TB0096Y | A011 | BJ | | ALL | | |
| 07BZ | | | | 0-0 | 49-61-11 | D04952J | | DED | | TB0096Y | DED | | | ALL | | |
| 07C | 22 | | PQ | 7-0 | 49-61-11 | D04952J | | 18 | | TB0096X | A009 | BJ | | ALL | | |
| 07CZ | | | | 0-0 | 49-61-11 | D04952J | | DED | | TB0096X | DED | | | ALL | | |
| 082 | 20 | | PA | 8-0 | 21-33-21 | D01778 | | 2 | | GD00265 | S.. | 2 | | ALL | | |
| 083 | 24 | | PK | 8-0 | 21-33-21 | D01778 | | 3 | | D05012P | 9 | | | ALL | | |
| 084 | 20 | | PA | 8-0 | 21-33-21 | D01778 | | 4 | | GD00265 | A.. | 2 | | ALL | | |
| 086 | 24 | | PK | 15-0 | 21-33-21 | D01778 | | 6 | | D04854J | 24 | | | ALL | | |
| 087 | 24 | | PK | 15-0 | 21-33-21 | D01778 | | 7 | | D04854J | 25 | | | ALL | | |
| 088 | 24 | | PK | 15-0 | 21-33-21 | D01778 | | 8 | | D04854J | 12 | | | ALL | | |
| 089 | 24 | | PK | 15-0 | 21-33-21 | D01778 | | 9 | | D04854J | 13 | | | ALL | | |
| 08K | 24 | | PK | 6-0 | 73-21-18 | D07980J | | 33 | | D04774J | 47 | | | ALL | | |
| 08L | 24 | | PK | 6-0 | 73-21-18 | D07980J | | 34 | | D04774J | 48 | | | ALL | | |
| 08M | 24 | | PK | 15-0 | 74-31-11 | D05010P | | 22 | | D05410J | 16 | | | ALL | | |
| 08N | 20 | | PQ | 6-0 | 76-11-11 | D07982J | | 35 | | D05042J | 39 | | | ALL | | |
| 08NZ | | | | 0-0 | 76-11-11 | D07982J | | DED | | D05042J | DED | | | ALL | | |
| 08P | 20 | | PQ | 4-0 | 76-11-11 | D04774J | | 27 | | D05042J | 40 | | | ALL | | |
| 08PZ | | | | 0-0 | 76-11-11 | D05042J | | DED | | D04774J | DED | | | ALL | | |
| 08R | 20 | | PQ | 4-0 | 76-11-11 | D04774J | | 1 | | D05042J | 41 | | | ALL | | |
| 08RZ | | | | 0-0 | 76-11-11 | D05042J | | DED | | D04774J | DED | | | ALL | | |
| 08U | 24 | | PV | 6-0 | 78-34-11 | D05042J | | 47 | | TB0098Y | C012 | BJ | | ALL | | |
| 08UZ | | | | 0-0 | 78-34-11 | D05042J | | DED | | TB0098Y | DED | | | ALL | | |
| 08V | 24 | | PV | 6-0 | 78-34-11 | D05042J | | 46 | | TB0098X | B006 | BJ | | ALL | | |
| 08VZ | | | | 0-0 | 78-34-11 | D05042J | | DED | | TB0098X | DED | | | ALL | | |
| 09K | 24 | | PV | 6-0 | 73-21-18 | D07982J | | 33 | | D04938J | 16 | | | ALL | | |
| 09KZ | | | | 0-0 | 73-21-18 | D07982J | | DED | | D04938J | DED | | | ALL | | |
| 09L | 24 | | PV | 6-0 | 73-21-18 | D07982J | | 34 | | D04938J | 17 | | | ALL | | |
| 09LZ | | | | 0-0 | 73-21-18 | D07982J | | DED | | D04938J | DED | | | ALL | | |
| 09N | 20 | | PA | 6-0 | 76-11-11 | D07980J | | 35 | | D04952J | 51 | | | ALL | | |
| 09P | 20 | | PA | 4-0 | 76-11-11 | D04756J | | 25 | | D04952J | 52 | | | ALL | | |
| 09R | 20 | | PA | 4-0 | 76-11-11 | D04756J | | 1 | | D04952J | 53 | | | ALL | | |
| 09T | 24 | | PK | 6-0 | 73-21-14 | D07982J | | 37 | | D05784J | 14 | | | 050-099, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 5

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|--|-------|------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0070 | 286T0070 | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 09T | 24 | PK | | 7-0 | 73-21-14 | D07982J | | 37 | | D05784J | | 14 | | 150-199 | |
| 09U | 24 | PV | TO | 7-0 | 78-34-21 | D04952J | | 55 | | TB0104Y | C012 | BJ | | ALL | |
| 09UZ | | | TO | 0-0 | 78-34-21 | D04952J | | DED | | TB0104Y | DED | | | ALL | |
| 09V | 24 | PV | TP | 7-0 | 78-34-21 | D04952J | | 31 | | TB0104X | B006 | BJ | | ALL | |
| 09VZ | | | TP | 0-0 | 78-34-21 | D04952J | | DED | | TB0104X | DED | | | ALL | |
| 101 | 22 | PQ | S | 6-0 | 31-31-26 | TB0098X | | A002 | BJ | D05042J | | 24 | | 050-099 | |
| 101 | 22 | PQ | S | 6-0 | 31-31-26 | D05042J | | 24 | | TB0098X | A002 | BJ | | 150-199, 275-299 | |
| 101Z | | | S | 0-0 | 31-31-26 | TB0098X | | DED | | D05042J | DED | | | 050-099 | |
| 101Z | | | S | 0-0 | 31-31-26 | D05042J | | DED | | TB0098X | DED | | | 150-199, 275-299 | |
| 102 | 22 | PQ | U | 6-0 | 31-31-26 | TB0104X | | B005 | BJ | D04852J | | 1 | | 050-099 | |
| 102 | 22 | PQ | U | 7-0 | 31-31-26 | D04852J | | 1 | | TB0104X | B005 | BJ | | 150-199, 275-299 | |
| 102Z | | | U | 0-0 | 31-31-26 | TB0104X | | DED | | D04852J | DED | | | 050-099 | |
| 102Z | | | U | 0-0 | 31-31-26 | D04852J | | DED | | TB0104X | DED | | | 150-199, 275-299 | |
| 105 | 22 | PA | | 7-0 | 74-31-11 | D00886 | | 5 | | D05010P | | 21 | | ALL | |
| 106 | 22 | PA | | 11-0 | 74-31-11 | D00886 | | 2 | | TB0098Y | A012 | BJ | | ALL | |
| 107 | 22 | PA | | 11-0 | 74-31-11 | D00886 | | 7 | | TB0098Y | A012 | BJ | | ALL | |
| 108 | 22 | PA | | 11-0 | 74-31-11 | D00886 | | 8 | | TB0098X | C006 | BJ | | ALL | |
| 109 | 24 | PK | | 11-0 | 74-31-11 | D00886 | | 9 | | TB0098X | D006 | BJ | | ALL | |
| 10A | 18 | PQ | FA | 8-0 | 80-11-11 | D07982J | | 38 | DL | D06162P | | 31 | DK | ALL | |
| 10AZ | | | FA | 0-0 | 80-11-11 | D07982J | | DED | | D06162P | DED | | | ALL | |
| 10B | 24 | PV | FB | 9-0 | 80-11-11 | D06162P | | 32 | | TB0106X | A005 | BJ | | ALL | |
| 10BZ | | | FB | 0-0 | 80-11-11 | D06162P | | DED | | TB0106X | DED | | | ALL | |
| 10C | 24 | PV | FC | 9-0 | 80-11-11 | D06162P | | 33 | | TB0106X | A006 | BJ | | ALL | |
| 10CZ | | | FC | 0-0 | 80-11-11 | D06162P | | DED | | TB0106X | DED | | | ALL | |
| 10D | 24 | PV | FD | 6-0 | 80-11-11 | D06162P | | 34 | | D04774J | | 22 | | ALL | |
| 10DZ | | | FD | 0-0 | 80-11-11 | D06162P | | DED | | D04774J | DED | | | ALL | |
| 10E | 24 | PV | FE | 6-0 | 80-11-11 | D06162P | | 35 | | D04774J | | 6 | | ALL | |
| 10EZ | | | FE | 0-0 | 80-11-11 | D06162P | | DED | | D04774J | DED | | | ALL | |
| 10F | 24 | PV | FF | 10-0 | 80-11-11 | D06162P | | 36 | | TB0106Y | A029 | BJ | | 050-099 | |
| 10F | 24 | PV | FF | 9-0 | 80-11-11 | D06162P | | 36 | | TB0106Y | A029 | BJ | | 150-199, 275-299 | |
| 10FZ | | | FF | 0-0 | 80-11-11 | D06162P | | DED | | TB0106Y | DED | | | ALL | |
| 10G | 24 | PV | FG | 6-0 | 80-11-11 | D06162P | | 37 | | D04774J | | 23 | | ALL | |
| 10GZ | | | FG | 0-0 | 80-11-11 | D06162P | | DED | | D04774J | DED | | | ALL | |
| 10H | 18 | PQ | GA | 6-0 | 80-11-11 | D06162P | | 38 | DK | D04774J | | 7 | DK | ALL | |
| 10HZ | | | GA | 0-0 | 80-11-11 | D06162P | | DED | | D04774J | DED | | | ALL | |
| 10J | 24 | PV | GB | 6-0 | 80-11-11 | D06162P | | 39 | | D04774J | | 10 | | ALL | |
| 10JZ | | | GB | 0-0 | 80-11-11 | D06162P | | DED | | D04774J | DED | | | ALL | |
| 10K | 22 | PA | | 4-0 | 80-11-11 | D06162P | | 40 | | D04952J | | 15 | | ALL | |
| 10L | 24 | PV | GD | 6-0 | 80-11-11 | D06162P | | 41 | | D04774J | | 9 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 6

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 10LZ | | | | GD | 0-0 | 80-11-11 | D06162P | DED | | | | D04774J | DED | | ALL |
| 10M | 24 | PK | | | 8-0 | 80-11-11 | D07982J | 39 | | | | D06162P | 42 | | ALL |
| 10N | 22 | PA | | | 8-0 | 23-22-11 | D04010P | 28 | | | | D04774J | 4 | | 050-099 |
| 10N | 22 | PA | | | 7-0 | 23-22-11 | D04010P | 28 | | | | D04774J | 4 | | 150-199, 275-299 |
| 10R | 24 | PK | | | 6-0 | 22-11-32 | D04010P | 19 | | | | D04541J | 1 | | ALL |
| 10S | 24 | PK | | | 6-0 | 22-11-32 | D04010P | 20 | | | | D04541J | 2 | | ALL |
| 10V | 24 | PV | FP | | 7-0 | 80-11-11 | TB0106Y | A029 | BJ | | | D04774J | 5 | | 050-099 |
| 10V | 24 | PV | FP | | 7-0 | 80-11-11 | D04774J | 5 | | | | TB0106Y | A029 | BJ | 150-199, 275-299 |
| 10VZ | | | FP | | 0-0 | 80-11-11 | TB0106Y | DED | | | | D04774J | DED | | 050-099 |
| 10VZ | | | FP | | 0-0 | 80-11-11 | D04774J | DED | | | | TB0106Y | DED | | 150-199, 275-299 |
| 110 | 18 | PQ | GE | | 16-0 | 80-11-11 | D00886 | 10 | DK | | | D06162P | 28 | DK | ALL |
| 110Z | | | GE | | 0-0 | 80-11-11 | D00886 | DED | | | | D06162P | DED | | ALL |
| 111 | 18 | PA | | | 16-0 | 80-11-11 | D00886 | 11 | DK | | | D06162P | 29 | DK | ALL |
| 112 | 24 | PV | GF | | 16-0 | 80-11-11 | D00886 | 12 | | | | D06162P | 30 | | ALL |
| 112Z | | | GF | | 0-0 | 80-11-11 | D00886 | DED | | | | D06162P | DED | | ALL |
| 11A | 18 | PA | | | 8-0 | 80-11-21 | D07980J | 38 | DL | | | D06160P | 31 | DK | ALL |
| 11B | 24 | PK | | | 4-0 | 80-11-21 | D06160P | 32 | | | | D05410J | 5 | | ALL |
| 11C | 24 | PK | | | 4-0 | 80-11-21 | D06160P | 33 | | | | D05410J | 6 | | ALL |
| 11D | 24 | PK | | | 5-0 | 80-11-21 | D06160P | 34 | | | | D04938J | 18 | | ALL |
| 11E | 24 | PK | | | 6-0 | 80-11-21 | D06160P | 35 | | | | D04756J | 4 | | ALL |
| 11F | 24 | PK | | | 10-0 | 80-11-21 | D06160P | 36 | | | | TB0106Y | C029 | BJ | 050-099 |
| 11F | 24 | PK | | | 9-0 | 80-11-21 | D06160P | 36 | | | | TB0106Y | C029 | BJ | 150-199, 275-299 |
| 11G | 24 | PK | | | 5-0 | 80-11-21 | D06160P | 37 | | | | D04938J | 22 | | ALL |
| 11H | 18 | PA | | | 6-0 | 80-11-21 | D06160P | 38 | DK | | | D04756J | 5 | DK | ALL |
| 11J | 24 | PK | | | 6-0 | 80-11-21 | D06160P | 39 | | | | D04756J | 8 | | ALL |
| 11L | 24 | PK | | | 6-0 | 80-11-21 | D06160P | 41 | | | | D04756J | 7 | | ALL |
| 11P | 20 | PA | | | 6-0 | 27-41-11 | D07980J | 40 | | | | D04774J | 15 | | ALL |
| 11R | 20 | PA | | | 6-0 | 27-41-21 | D07982J | 40 | | | | D04756J | 19 | | ALL |
| 11S | 24 | PK | | | 8-0 | 31-25-11 | D04010P | 23 | | | | D05792J | 15 | | ALL |
| 11T | 24 | PK | | | 8-0 | 31-25-11 | D04010P | 22 | | | | D05784J | 15 | | ALL |
| 11U | 12 | PA | | | 7-0 | 34-21-11 | D05854J | 1 | | | | D04008P | 1 | | ALL |
| 11V | 24 | PK | | | 7-0 | 80-11-21 | TB0106Y | C029 | BJ | | | D04756J | 3 | | 050-099 |
| 11V | 24 | PK | | | 7-0 | 80-11-21 | D04756J | 3 | | | | TB0106Y | C029 | BJ | 150-199, 275-299 |
| 11W | 12 | PA | | | 7-0 | 34-21-31 | D04938J | 15 | | | | D04010P | 1 | | ALL |
| 11X | 20 | PA | | | 4-0 | 22-21-11 | D05012P | 6 | | | | TB0068X | B010 | BJ | ALL |
| 11Y | 12 | PA | | | 5-0 | 34-21-21 | D04940J | 56 | | | | D05828P | 1 | | ALL |
| 120 | 22 | PQ | AF | | 4-0 | 21-28-11 | D07980J | 5 | | | | TB0104X | D008 | BJ | 050-099 |
| 120 | 22 | PA | | | 4-0 | 21-28-11 | D07980J | 5 | | | | TB0104X | D008 | BJ | 150-199, 275-299 |
| 120Z | | | AF | | 0-0 | 21-28-11 | D07980J | DED | | | | TB0104X | DED | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 7

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 123 | 20 | PQ | W | 8-0 | 78-34-11 | D07980J | 14 | | | TB0098Y | C016 | BJ | | ALL | |
| 123Z | | | W | 0-0 | 78-34-11 | D07980J | DED | | | TB0098Y | DED | | | ALL | |
| 124 | 20 | PA | | 8-0 | 78-34-21 | TB0104Y | C014 | BJ | | D04774J | 36 | | | ALL | |
| 126 | 20 | PQ | X | 8-0 | 78-34-11 | TB0098Y | C016 | BJ | | D04774J | 25 | | | ALL | |
| 126Z | | | X | 0-0 | 78-34-11 | TB0098Y | DED | | | D04774J | DED | | | ALL | |
| 127 | 20 | PQ | Y | 8-0 | 78-34-11 | TB0098Y | C016 | BJ | | D05854J | 19 | | | ALL | |
| 127Z | | | Y | 0-0 | 78-34-11 | TB0098Y | DED | | | D05854J | DED | | | ALL | |
| 128 | 20 | PA | | 8-0 | 78-34-21 | TB0104Y | C014 | BJ | | D04756J | 23 | | | ALL | |
| 129 | 20 | PA | | 8-0 | 78-34-21 | TB0104Y | C014 | BJ | | D07982J | 20 | | | ALL | |
| 12A | 24 | PK | | 5-0 | 24-22-11 | TB0098X | A004 | BJ | | D05042J | 28 | | | ALL | |
| 12B | 24 | PK | | 5-0 | 24-22-11 | TB0098X | B004 | BJ | | D05042J | 29 | | | ALL | |
| 12C | 18 | PA | | 9-0 | 33-11-16 | L00673 | = G | C | | GD04424 | A.. | 2 | | ALL | |
| 12D | 18 | PA | | 10-0 | 33-11-16 | L00674 | = G | C | | GD04424 | A.. | 2 | | ALL | |
| 12E | 18 | PA | | 9-0 | 25-63-11 | D04010P | 31 | DL | | TB0096G | 16 | 2 | | 050-099 | |
| 12E | 18 | PA | | 10-0 | 25-63-11 | D04010P | 31 | DL | | TB0096G | 16 | 2 | | 150-199, 275-299 | |
| 12F | 18 | PA | | 6-0 | 25-63-11 | TB0096G | 16 | 2 | | D08104J | 4 | DK | | 050-099 | |
| 12F | 18 | PA | | 6-0 | 25-63-11 | D08104J | 4 | DK | | TB0096G | 16 | 2 | | 150-199, 275-299 | |
| 12G | 24 | PK | | 6-0 | 73-21-15 | D04774J | 16 | | | D07980J | 39 | | | ALL | |
| 12S | 24 | PK | | 7-0 | 35-21-11 | D05410J | 3 | | | TB0106X | A007 | BJ | | ALL | |
| 12Z | 22 | PA | | 8-0 | 33-13-16 | D05010P | 9 | | | TB0064X | A018 | BJ | | ALL | |
| 133 | 22 | PQ | SI | 7-0 | 33-16-17 | TB0070Y | C021 | BJ | | D00852 | 3 | | | 050-099, 155-199 | |
| 133 | 22 | PQ | SI | 8-0 | 33-16-17 | TB0070Y | C021 | BJ | | D00852 | 3 | | | 150-154 | |
| 133 | 22 | PQ | SI | 7-0 | 33-16-17 | TB0068Y | A019 | BJ | | D00852 | 3 | | | 275-299 | |
| 133Z | | | SI | 0-0 | 33-16-17 | TB0070Y | DED | | | D00852 | DED | | | 050-099, 150-199 | |
| 133Z | | | SI | 0-0 | 33-16-17 | TB0068Y | DED | | | D00852 | DED | | | 275-299 | |
| 134 | 22 | PA | | 7-0 | 33-16-17 | TB0068Z | 22 | BJ | | D00852 | 4 | | | ALL | |
| 135 | 22 | PQ | FJ | 7-0 | 74-31-21 | D00852 | 5 | | | D05012P | 21 | | | ALL | |
| 135Z | | | FJ | 0-0 | 74-31-21 | D00852 | DED | | | D05012P | DED | | | ALL | |
| 136 | 22 | PQ | FK | 12-0 | 74-31-21 | D00852 | 23 | | | TB0104Y | A012 | BJ | | ALL | |
| 136Z | | | FK | 0-0 | 74-31-21 | D00852 | DED | | | TB0104Y | DED | | | ALL | |
| 137 | 22 | PQ | FL | 12-0 | 74-31-21 | D00852 | 7 | | | TB0104Y | A012 | BJ | | ALL | |
| 137Z | | | FL | 0-0 | 74-31-21 | D00852 | DED | | | TB0104Y | DED | | | ALL | |
| 138 | 22 | PQ | FM | 12-0 | 74-31-21 | D00852 | 8 | | | TB0104X | C006 | BJ | | ALL | |
| 138Z | | | FM | 0-0 | 74-31-21 | D00852 | DED | | | TB0104X | DED | | | ALL | |
| 139 | 24 | PV | FN | 12-0 | 74-31-21 | D00852 | 9 | | | TB0104X | D006 | BJ | | ALL | |
| 139Z | | | FN | 0-0 | 74-31-21 | D00852 | DED | | | TB0104X | DED | | | ALL | |
| 13E | 18 | PA | | 8-0 | 28-41-12 | D07982J | 11 | DL | | D04854J | 6 | | | ALL | |
| 13F | 20 | PA | | 5-0 | 21-31-11 | D05012P | 10 | | | TB0068X | A012 | BJ | | ALL | |
| 13G | 24 | PK | | 12-0 | 21-58-16 | TB0066Y | C015 | BJ | | D05854J | 14 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 8

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 13H | 24 | | PK | 6-0 | 21-58-12 | D07984J | | 33 | | | | | D05854J | 11 | | | ALL |
| 13J | 24 | | PK | 6-0 | 21-58-12 | TB0106X | | C010 | BJ | | | | D05854J | 12 | | | ALL |
| 13M | 24 | | PK | 6-0 | 21-58-16 | TB0098Y | | A011 | BJ | | | | D05410J | 32 | | | ALL |
| 13N | 22 | | PA | 6-0 | 21-58-16 | TB0098Y | | A011 | BJ | | | | D05854J | 15 | | | ALL |
| 13P | 22 | | PA | 6-0 | 21-58-16 | TB0106X | | D010 | BJ | | | | D05854J | 16 | | | ALL |
| 140 | 18 | | PA | 16-0 | 80-11-21 | D00852 | | 10 | DK | | | | D06160P | 28 | DK | | ALL |
| 141 | 18 | | PA | 16-0 | 80-11-21 | D00852 | | 11 | DK | | | | D06160P | 29 | DK | | ALL |
| 142 | 24 | | PK | 16-0 | 80-11-21 | D00852 | | 12 | | | | | D06160P | 30 | | | ALL |
| 144 | 24 | | PK | 14-0 | 29-21-31 | D00852 | | 14 | | | | | D05042J | 30 | | | ALL |
| 145 | 24 | | PK | 14-0 | 29-21-31 | D00852 | | 15 | | | | | D05042J | 35 | | | ALL |
| 146 | 24 | | PK | 18-0 | 29-21-31 | D04010P | | 26 | | | | | D00852 | 16 | | | ALL |
| 147 | 24 | | PK | 14-0 | 29-21-31 | D05042J | | 17 | | | | | D00852 | 17 | | | ALL |
| 148 | 24 | | PK | 14-0 | 29-21-31 | D05042J | | 9 | | | | | D00852 | 18 | | | ALL |
| 149 | 24 | | PK | 14-0 | 29-21-31 | D05042J | | 18 | | | | | D00852 | 19 | | | ALL |
| 14A | 20 | | PA | 5-0 | 33-11-13 | TB0070Y | | C016 | BJ | | | | D05010P | 2 | | | ALL |
| 14B | 20 | | PA | 16-0 | 33-11-13 | TB0070Y | | C016 | BJ | | | | D06160P | 50 | | | ALL |
| 14C | 20 | | PA | 8-0 | 33-11-13 | D07980J | | 25 | | | | | D06160P | 51 | | | ALL |
| 14D | 24 | | PK | 7-0 | 33-11-13 | TB0098X | | B008 | BJ | | | | D06160P | 53 | | | ALL |
| 15A | 24 | | PK | 6-0 | 73-21-15 | D04852J | | 4 | | | | | TB0098X | C008 | BJ | | ALL |
| 195 | 20 | | PA | 6-0 | 73-21-11 | D04774J | | 50 | | | | | TB0104X | A010 | BJ | | 050-099 |
| 195 | 20 | | PA | 6-0 | 73-21-11 | TB0104X | | A010 | BJ | | | | D04774J | 50 | | | 150-199, 275-299 |
| 196 | 20 | | PA | 6-0 | 73-21-11 | D04756J | | 40 | | | | | TB0104X | B010 | BJ | | 050-099 |
| 196 | 20 | | PA | 6-0 | 73-21-11 | TB0104X | | B010 | BJ | | | | D04756J | 40 | | | 150-199, 275-299 |
| 201B | 24 | | PL | IA | 6-0 | 24-34-11 | | 20 | | | | | D05410J | 23 | | | ALL |
| 201R | 24 | | PL | IA | 0-0 | 24-34-11 | | 21 | | | | | D05410J | 22 | | | ALL |
| 202B | 24 | | PL | IB | 6-0 | 24-34-11 | | 22 | | | | | D05410J | 25 | | | ALL |
| 202R | 24 | | PL | IB | 0-0 | 24-34-11 | | 23 | | | | | D05410J | 24 | | | ALL |
| 203B | 24 | | PL | IC | 6-0 | 24-34-11 | | 24 | | | | | D05410J | 27 | | | ALL |
| 203R | 24 | | PL | IC | 0-0 | 24-34-11 | | 25 | | | | | D05410J | 26 | | | ALL |
| 209B | 24 | | PL | II | 7-0 | 28-41-11 | | D001 | BJ | | | | D04940J | 39 | | | ALL |
| 209R | 24 | | PL | II | 0-0 | 28-41-11 | | D002 | BJ | | | | D04940J | 41 | | | ALL |
| 216B | 24 | | PL | IP | 15-0 | 28-41-11 | | 39 | | | | | D04940J | 12 | | | ALL |
| 216R | 24 | | PL | IP | 0-0 | 28-41-11 | | 20 | | | | | D04940J | 13 | | | ALL |
| 217B | 24 | | PL | IQ | 15-0 | 28-41-11 | | 18 | | | | | D04940J | 14 | | | ALL |
| 217R | 24 | | PL | IQ | 0-0 | 28-41-11 | | 19 | | | | | D04940J | 15 | | | ALL |
| 218B | 24 | | PL | IR | 15-0 | 28-41-11 | | 16 | | | | | D04940J | 16 | | | ALL |
| 218R | 24 | | PL | IR | 0-0 | 28-41-11 | | 32 | | | | | D04940J | 17 | | | ALL |
| 219B | 24 | | PL | IS | 15-0 | 28-41-11 | | 24 | | | | | D04940J | 19 | | | ALL |
| 219R | 24 | | PL | IS | 0-0 | 28-41-11 | | 10 | | | | | D04940J | 20 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 9

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0070 | 286T0070 | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 220B | 24 | PL | IT | | 15-0 | 28-41-11 | D03898 | | 11 | | D04940J | | 21 | | ALL |
| 220R | 24 | PL | IT | | 0-0 | 28-41-11 | D03898 | | 12 | | D04940J | | 22 | | ALL |
| 221B | 24 | PL | IU | | 15-0 | 28-41-11 | D03898 | | 13 | | D04940J | | 23 | | ALL |
| 221R | 24 | PL | IU | | 0-0 | 28-41-11 | D03898 | | 29 | | D04940J | | 24 | | ALL |
| 222B | 24 | PL | IV | | 15-0 | 28-41-11 | D03900 | | 39 | | D04940J | | 26 | | ALL |
| 222R | 24 | PL | IV | | 0-0 | 28-41-11 | D03900 | | 20 | | D04940J | | 27 | | ALL |
| 223B | 24 | PL | IW | | 15-0 | 28-41-11 | D03900 | | 18 | | D04940J | | 28 | | ALL |
| 223R | 24 | PL | IW | | 0-0 | 28-41-11 | D03900 | | 19 | | D04940J | | 29 | | ALL |
| 224B | 24 | PL | IX | | 15-0 | 28-41-11 | D03900 | | 16 | | D04940J | | 30 | | ALL |
| 224R | 24 | PL | IX | | 0-0 | 28-41-11 | D03900 | | 32 | | D04940J | | 31 | | ALL |
| 225B | 24 | PL | IY | | 15-0 | 28-41-11 | D03900 | | 24 | | D04940J | | 33 | | ALL |
| 225R | 24 | PL | IY | | 0-0 | 28-41-11 | D03900 | | 10 | | D04940J | | 34 | | ALL |
| 226B | 24 | PL | JA | | 15-0 | 28-41-11 | D03900 | | 11 | | D04940J | | 35 | | ALL |
| 226R | 24 | PL | JA | | 0-0 | 28-41-11 | D03900 | | 12 | | D04940J | | 36 | | ALL |
| 227B | 24 | PL | JB | | 15-0 | 28-41-11 | D03900 | | 13 | | D04940J | | 37 | | ALL |
| 227R | 24 | PL | JB | | 0-0 | 28-41-11 | D03900 | | 29 | | D04940J | | 38 | | ALL |
| 228B | 24 | PL | JC | | 3-0 | 35-11-13 | D05410J | | 35 | | D04772J | | 8 | | ALL |
| 228R | 24 | PL | JC | | 0-0 | 35-11-13 | D05410J | | 36 | | D04772J | | 9 | | ALL |
| 301B | 22 | PC | MA | | 13-0 | 21-31-31 | D01408 | | 4 | | TB0098Y | C015 | BJ | | 050-099 |
| 301B | 22 | PC | MA | | 12-0 | 21-31-31 | D01408 | | 4 | | TB0098Y | C015 | BJ | | 150-199, 275-299 |
| 301R | 22 | PC | MA | | 0-0 | 21-31-31 | D01408 | | 5 | | TB0098Y | A015 | BJ | | ALL |
| 301Y | 22 | PC | MA | | 0-0 | 21-31-31 | D01408 | | 6 | | TB0098Y | A016 | BJ | | ALL |
| 302B | 24 | PM | MB | | 15-0 | 33-11-13 | D00840 | | 9 | | D05792J | | 8 | | ALL |
| 302R | 24 | PM | MB | | 0-0 | 33-11-13 | D00840 | | 7 | | D05792J | | 9 | | ALL |
| 302Y | 24 | PM | MB | | 0-0 | 33-11-13 | D00840 | | 8 | | D05792J | | 10 | | ALL |
| 305B | 22 | PC | ME | | 6-0 | 21-31-31 | TB0098Y | C015 | BJ | | D08054J | | 4 | | ALL |
| 305R | 22 | PC | ME | | 0-0 | 21-31-31 | TB0098Y | A015 | BJ | | D08054J | | 5 | | ALL |
| 305Y | 22 | PC | ME | | 0-0 | 21-31-31 | TB0098Y | A016 | BJ | | D08054J | | 6 | | ALL |
| 306B | 24 | PM | MC | | 4-0 | 49-94-14 | D04852J | | 22 | | D05410J | | 37 | | 050-099, 150-199 |
| 306B | 24 | PM | MC | | 5-0 | 49-94-14 | D04852J | | 22 | | D05410J | | 37 | | 275-299 |
| 306R | 24 | PM | MC | | 0-0 | 49-94-14 | D04852J | | 21 | | D05410J | | 38 | | ALL |
| 306Y | 24 | PM | MC | | 0-0 | 49-94-14 | D04852J | | 23 | | D05410J | | 39 | | ALL |
| 509 | 22 | PA | | | 12-0 | 28-22-31 | D01384 | | 21 | | TB0104X | C037 | BJ | | ALL |
| 50E | 24 | PK | | | 8-0 | 33-16-11 | TB0106Y | C013 | BJ | | D06162P | | 7 | | ALL |
| 510 | 22 | PQ | AJ | | 8-0 | 28-22-31 | TB0104Y | C036 | BJ | | D04854J | | 4 | | 050-099 |
| 510 | 22 | PQ | AQ | | 8-0 | 28-22-31 | TB0104Y | C036 | BJ | | D04854J | | 4 | | 150-199, 275-299 |
| 510Z | | | AJ | | 0-0 | 28-22-31 | TB0104Y | DED | | | D04854J | DED | | | 050-099 |
| 510Z | | | AQ | | 0-0 | 28-22-31 | TB0104Y | DED | | | D04854J | DED | | | 150-199, 275-299 |
| 525 | 24 | PK | | | 15-0 | 28-41-11 | D03900 | | 25 | | D04940J | | 32 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 10

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 538 | 24 | | PK | 15-0 | 28-41-11 | D03900 | | 38 | | | | | D04940J | 25 | | | ALL |
| 565 | 24 | | PK | 15-0 | 28-41-11 | D03898 | | 25 | | | | | D04940J | 18 | | | ALL |
| 578 | 24 | | PK | 15-0 | 28-41-11 | D03898 | | 38 | | | | | D04940J | 11 | | | ALL |
| 583 | 22 | | PA | 8-0 | 33-16-17 | TB0068Z | | 13 | BJ | | | | D01384 | 3 | | | ALL |
| 584 | 22 | | PA | 8-0 | 33-16-17 | TB0068Z | | 16 | BJ | | | | D01384 | 4 | | | ALL |
| 585 | 22 | | PA | 15-0 | 28-22-31 | TB0104X | | D038 | BJ | | | | D05410J | 4 | | | ALL |
| 586 | 24 | | PK | 15-0 | 28-25-11 | D01384 | | 6 | | | | | D04854J | 29 | | | ALL |
| 587 | 22 | | PA | 15-0 | 28-22-31 | D01384 | | 7 | | | | | TB0104X | A037 | BJ | | ALL |
| 588 | 22 | | PA | 15-0 | 28-22-31 | D01384 | | 8 | | | | | D04854J | 5 | | | ALL |
| 589 | 22 | | PA | 15-0 | 28-22-31 | D01384 | | 9 | | | | | D04854J | 9 | | | ALL |
| 591 | 22 | | PA | 15-0 | 28-22-31 | TB0104X | | B037 | BJ | | | | D04854J | 31 | | | ALL |
| 593 | 24 | | PK | 7-0 | 28-22-11 | D01384 | | 13 | | | | | D05012P | 2 | | | ALL |
| 594 | 24 | | PK | 15-0 | 28-22-11 | D01384 | | 14 | | | | | D04940J | 42 | | | ALL |
| 595 | 24 | | PK | 15-0 | 28-25-11 | D01384 | | 15 | | | | | D05042J | 22 | | | ALL |
| 596 | 24 | | PK | 15-0 | 28-25-11 | D01384 | | 16 | | | | | D04854J | 30 | | | ALL |
| 597 | 24 | | PK | 15-0 | 28-25-11 | D01384 | | 17 | | | | | D04854J | 28 | | | ALL |
| 59A | 22 | | PA | 6-0 | SPARE | TB0106X | | B003 | BJ | | | | D04854J | 18 | | | 150-199, 275-299 |
| 604 | 22 | | PA | 15-0 | 28-22-31 | D01384 | | 2 | | | | | TB0104X | D037 | BJ | | ALL |
| 611 | 20 | | PA | 9-0 | 33-13-16 | D00840 | | 1 | | | | | TB0064G | 2 | 2 | | ALL |
| 612 | 20 | | PA | 7-0 | 33-13-16 | D00840 | | 2 | | | | | GD00110 | A.. | 2 | | ALL |
| 613 | 20 | | PA | 8-0 | 33-11-13 | TB0070Y | | C016 | BJ | | | | D00840 | 3 | | | ALL |
| 614 | 20 | | PA | 18-0 | 33-11-13 | D06160P | | 52 | | | | | D00840 | 4 | | | ALL |
| 615 | 24 | | PK | 10-0 | 33-11-15 | D05010P | | 3 | | | | | D00840 | 5 | | | ALL |
| 616 | 24 | | PK | 17-0 | 33-11-15 | D06160P | | 5 | | | | | D00840 | 6 | | | ALL |
| 620 | 24 | | PK | 8-0 | 33-42-21 | D00840 | | 10 | | | | | TB0070Y | C015 | BJ | | ALL |
| 621 | 24 | | PK | 8-0 | 33-42-21 | D00840 | | 11 | | | | | TB0070X | D001 | BJ | | ALL |
| 622 | 20 | | PA | 8-0 | 33-42-21 | D00840 | | 12 | | | | | TB0070X | D003 | BJ | | 050-099 |
| 622 | 18 | | PA | 8-0 | 33-42-21 | D00840 | | 12 | DK | | | | TB0070F | C007 | 2 | | 150-199, 275-299 |
| 623 | 20 | | PA | 8-0 | 33-42-21 | D00840 | | 13 | | | | | TB0070X | D002 | BJ | | 050-099 |
| 623 | 18 | | PA | 8-0 | 33-42-21 | D00840 | | 13 | DK | | | | TB0070F | A007 | 2 | | 150-199, 275-299 |
| 631 | 20 | | PA | 9-0 | 33-13-16 | D00860 | | 1 | | | | | TB0064G | 2 | 2 | | ALL |
| 632 | 20 | | PA | 8-0 | 33-13-16 | D00860 | | 2 | | | | | GD00265 | A.. | 2 | | ALL |
| 635 | 20 | | PA | 8-0 | 33-16-11 | D00860 | | 5 | | | | | GD00265 | D.. | 2 | | ALL |
| 636 | 24 | | PK | 12-0 | 33-16-11 | D00860 | | 6 | | | | | TB0106Y | C013 | BJ | | ALL |
| 637 | 24 | | PK | 9-0 | 33-16-11 | TB0106Y | | C013 | BJ | | | | D06160P | 7 | | | ALL |
| 63G | 20 | | PQ | L | 6-0 | 78-34-11 | | 23 | | | | | TB0098X | A003 | BJ | | ALL |
| 63GZ | | | | L | 0-0 | 78-34-11 | | DED | | | | | TB0098X | DED | | | ALL |
| 63N | 20 | | PQ | M | 6-0 | 78-34-11 | | 25 | | | | | TB0098Y | C012 | BJ | | ALL |
| 63NZ | | | | M | 0-0 | 78-34-11 | | DED | | | | | TB0098Y | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 11

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 63R | 20 | | PA | 7-0 | 78-34-21 | D04952J | | 40 | | | TB0106Y | A028 | BJ | | 050-099, 150-154, 156-199, 275-299 |
| 63R | 20 | | PA | 7-0 | 78-34-21 | D04952J | | 40 | | | TB0106Y | A025 | BJ | | 155 |
| 63S | 20 | | PA | 10-0 | 78-34-21 | D04952J | | 39 | | | TB0104X | D027 | BJ | | 050-099, 150-166, 275-299 |
| 63S | 20 | | PA | 11-0 | 78-34-21 | D04952J | | 39 | | | TB0104X | D027 | BJ | | 167-199 |
| 641 | 22 | | PA | 9-0 | 33-11-16 | D00860 | | 11 | | | TB0066X | B003 | BJ | | ALL |
| 642 | 18 | | PA | 17-0 | 33-11-16 | D00860 | | 12 | DK | | SP02318 | | 9 | | ALL |
| 643 | 20 | | PA | 8-0 | 33-11-16 | D00860 | | 13 | | | GD00265 | A.. | 2 | | ALL |
| 645 | 16 | | PA | 8-0 | 33-11-14 | D06160P | | 3 | FM | | TB0096F | A015 | 2 | | ALL |
| 651 | 20 | | PA | 7-0 | 33-13-16 | D00838 | | 1 | | | TB0068H | | 3 | 2 | ALL |
| 652 | 20 | | PA | 6-0 | 33-13-16 | D00838 | | 2 | | | GD00265 | A.. | 2 | | ALL |
| 653 | 22 | | PA | 7-0 | 33-16-17 | TB0068Y | | | C019 | BJ | D00838 | | 3 | | ALL |
| 654 | 22 | | PA | 7-0 | 33-16-17 | TB0068Z | | | 22 | BJ | D00838 | | 4 | | ALL |
| 658 | 22 | | PA | 8-0 | 35-21-11 | D00838 | | 8 | | | D05010P | | 11 | | ALL |
| 659 | 24 | | PK | 8-0 | 35-21-11 | D00838 | | 9 | | | D05010P | | 12 | | ALL |
| 660 | 20 | | PA | 6-0 | 35-21-11 | D00838 | | 10 | | | GD00265 | D.. | 2 | | ALL |
| 661 | 22 | | PA | 14-0 | 33-51-11 | D00868 | | 1 | | | D05784J | | 17 | | ALL |
| 662 | 22 | | PA | 12-0 | 33-51-11 | D00868 | | 2 | | | TB0106X | C005 | BJ | | ALL |
| 663 | 22 | | PA | 12-0 | 33-51-11 | D00868 | | 3 | | | TB0106X | D005 | BJ | | ALL |
| 665 | 22 | | PA | 12-0 | 33-51-11 | D00868 | | 5 | | | TB0106X | C004 | BJ | | ALL |
| 666 | 22 | | PA | 12-0 | 33-51-11 | D00868 | | 6 | | | TB0106X | B005 | BJ | | ALL |
| 667 | 22 | | PA | 14-0 | 33-51-11 | D00868 | | 7 | | | D05784J | | 18 | | ALL |
| 668 | 22 | | PA | 8-0 | 33-51-11 | D00868 | | 8 | | | D05010P | | 5 | | ALL |
| 669 | 20 | | PA | 6-0 | 33-51-11 | D00868 | | 9 | | | GD00265 | D.. | 2 | | ALL |
| 670 | 20 | | PA | 6-0 | 33-51-11 | D00868 | | 10 | | | GD00265 | D.. | 2 | | ALL |
| 671 | 22 | | PA | 14-0 | 33-51-11 | D00868 | | 11 | | | D05784J | | 19 | | ALL |
| 672 | 24 | | PK | 12-0 | 33-51-11 | D00868 | | 12 | | | TB0106X | C003 | BJ | | ALL |
| 673 | 20 | | PA | 6-0 | 33-51-11 | D00868 | | 13 | | | GD00265 | D.. | 2 | | ALL |
| 674 | 22 | | PA | 12-0 | 33-51-11 | D00868 | | 14 | | | TB0106X | D004 | BJ | | ALL |
| 675 | 22 | | PA | 8-0 | 33-51-11 | D00868 | | 15 | | | D05010P | | 6 | | ALL |
| 676 | 22 | | PA | 12-0 | 33-51-11 | D00868 | | 16 | | | TB0106X | B004 | BJ | | ALL |
| 67H | 22 | | PQ | AB | 14-0 | 73-21-11 | | | A002 | BJ | D04774J | | 11 | | ALL |
| 67HZ | | | | AB | 0-0 | 73-21-11 | | | B002 | BJ | D04774J | | 14 | | 050-099, 162-199, 277-299 |
| 67HZ | | | | AB | 0-0 | 73-21-11 | | | DED | | D04774J | | 14 | | 150-157, 275-276 |
| 681 | 20 | | PA | 8-0 | 33-13-16 | D10216 | | 1 | | | TB0068H | | 6 | 2 | ALL |
| 682 | 20 | | PA | 7-0 | 33-13-16 | D10216 | | 2 | | | GD00110 | A.. | 2 | | ALL |
| 683 | 22 | | PA | 8-0 | 33-16-17 | D10216 | | 3 | | | TB0068Y | C017 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 12

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 684 | 22 | | PA | | 8-0 | 33-16-17 | D10216 | | 4 | | | | TB0068Z | 15 | BJ | | ALL |
| 685 | 24 | | PK | | 13-0 | 24-33-11 | D10216 | | 5 | | | | TB0106Y | C026 | BJ | | ALL |
| 686 | 24 | | PK | | 18-0 | 24-33-11 | D10216 | | 6 | | | | D04006P | 27 | | | ALL |
| 687 | 24 | | PK | | 18-0 | 24-33-11 | D10216 | | 7 | | | | D04006P | 23 | | | ALL |
| 688 | 20 | | PQ | SY | 7-0 | 49-61-11 | D10216 | | 8 | | | | GD00110 | D.. | 2 | | ALL |
| 688Z | | | | SY | 0-0 | 49-61-11 | D10216 | | DED | | | | GD00110 | DED | | | ALL |
| 68L | 22 | | PQ | AC | 12-0 | 73-21-11 | TB0066X | A002 | | BJ | | | D04756J | 6 | | | ALL |
| 68LZ | | | | AC | 0-0 | 73-21-11 | TB0066X | B002 | | BJ | | | D04756J | 2 | | | 050-099, 162-199, 277-299 |
| 68LZ | | | | AC | 0-0 | 73-21-11 | TB0066X | DED | | | | | D04756J | 2 | | | 150-157, 275-276 |
| 690 | 24 | | PK | | 18-0 | 24-33-11 | D10216 | | 10 | | | | D04006P | 19 | | | ALL |
| 691 | 20 | | PA | | 7-0 | 24-33-11 | D10216 | | 11 | | | | GD00110 | D.. | 2 | | ALL |
| 692 | 20 | | PA | | 7-0 | 24-33-11 | D10216 | | 12 | | | | GD00110 | D.. | 2 | | ALL |
| 693 | 24 | | PK | | 18-0 | 24-33-11 | D10216 | | 13 | | | | D04006P | 22 | | | ALL |
| 695 | 22 | | PQ | TC | 8-0 | 49-61-11 | D10216 | | 15 | | | | TB0064X | A017 | BJ | | ALL |
| 695Z | | | | TC | 0-0 | 49-61-11 | D10216 | | DED | | | | TB0064X | DED | | | ALL |
| 697 | 24 | | PK | | 13-0 | 24-31-11 | D10216 | | 17 | | | | TB0106Y | A026 | BJ | | ALL |
| 699 | 20 | | PA | | 7-0 | 24-33-11 | D10216 | | 19 | | | | GD00110 | D.. | 2 | | ALL |
| 700 | 18 | | PA | | 18-0 | 24-33-11 | D10216 | | 20 | DK | | | D04006P | 8 | | | ALL |
| 701 | 24 | | PK | | 18-0 | 24-33-11 | D10216 | | 21 | | | | D04006P | 21 | | | ALL |
| 702 | 20 | | PA | | 7-0 | 24-33-11 | D10216 | | 22 | | | | GD00110 | A.. | 2 | | ALL |
| 703 | 24 | | PK | | 18-0 | 24-33-11 | D10216 | | 23 | | | | D04006P | 20 | | | ALL |
| 705 | 24 | | PK | | 15-0 | 24-33-11 | D10216 | | 25 | | | | D05410J | 10 | | | ALL |
| 709 | 20 | | PA | | 7-0 | 24-31-41 | D10216 | | 29 | | | | GD00110 | D.. | 2 | | ALL |
| 70B | 20 | | PA | | 6-0 | 25-33-11 | D05042J | | 49 | | | | D04006P | 1 | | | 050-099, 155-199, 277-299 |
| 711 | 24 | | PK | | 15-0 | 24-31-41 | D10216 | | 31 | | | | D04952J | 41 | | | ALL |
| 712 | 20 | | PA | | 7-0 | 24-33-11 | D10216 | | 32 | | | | GD00267 | D.. | 2 | | ALL |
| 714 | 24 | | PK | | 18-0 | 24-33-11 | D10216 | | 34 | | | | D04006P | 26 | | | ALL |
| 721R | 22 | | PH | | 6-0 | 26-15-11 | D07982J | | 6 | | | | D04952J | 21 | | | ALL |
| 722R | 22 | | PH | | 6-0 | 26-15-11 | D07980J | | 6 | | | | D05042J | 21 | | | ALL |
| 723R | 22 | | PH | | 7-0 | 26-15-11 | TB0106Y | A024 | | BJ | | | D04952J | 28 | | | ALL |
| 724R | 22 | | PH | | 6-0 | 26-15-12 | D07982J | | 1 | | | | D04952J | 35 | | | ALL |
| 725 | 22 | | PA | | 7-0 | 49-61-11 | TB0096X | B009 | | BJ | | | D04952J | 34 | | | ALL |
| 741 | 18 | | PA | | 18-0 | 24-11-11 | D04006P | | 4 | | | | D01346 | 1 | | | ALL |
| 743 | 18 | | PA | | 18-0 | 24-11-21 | D04008P | | 4 | | | | D01346 | 3 | | | ALL |
| 744 | 22 | | PQ | EA | 7-0 | 28-31-12 | D04774J | | 38 | | | | TB0096D | C033 | 2 | | 050 |
| 744 | 22 | | PQ | EA | 20-0 | 28-31-12 | TB0096D | C033 | | 2 | | | D04774J | 38 | | | 051-099 |
| 744 | 22 | | PQ | EA | 9-0 | 28-31-12 | D04774J | | 38 | | | | TB0096D | C033 | 2 | | 155-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 13

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 744Z | | | | EA | 0-0 | 28-31-12 | D04774J | | DED | | TB0096D | | DED | | 050, 155-199, 277-299 |
| 744Z | | | | EA | 0-0 | 28-31-12 | TB0096D | | DED | | D04774J | | DED | | 051-099 |
| 746 | 18 | | PA | | 15-0 | 24-11-11 | D01346 | | 6 | | D05854J | | 6 | | ALL |
| 750 | 18 | | PA | | 15-0 | 24-11-21 | D01346 | | 10 | | D04756J | | 11 | DK | ALL |
| 762R | 22 | | PH | | 6-0 | 26-11-11 | D07980J | | 4 | | D05042J | | 11 | | ALL |
| 763R | 22 | | PH | | 5-0 | 26-11-11 | D07980J | | 2 | | TB0106Y | A024 | BJ | | ALL |
| 764R | 22 | | PH | | 7-0 | 26-11-11 | D05042J | | 12 | | TB0106Y | A024 | BJ | | ALL |
| 765R | 22 | | PH | | 7-0 | 26-11-11 | D05042J | | 13 | | TB0096D | A028 | 2 | | ALL |
| 766R | 22 | | PH | | 7-0 | 26-11-11 | D04774J | | 18 | | TB0096D | A029 | 2 | | ALL |
| 767R | 22 | | PH | | 7-0 | 26-11-11 | D05042J | | 14 | | TB0096D | C027 | 2 | | ALL |
| 768R | 22 | | PH | | 4-0 | 26-11-11 | D05042J | | 15 | | D05784J | | 16 | | ALL |
| 769R | 22 | | PH | | 6-0 | 26-11-12 | D07984J | | 3 | | D04938J | | 6 | | ALL |
| 770R | 22 | | PH | | 6-0 | 26-11-12 | D07980J | | 3 | | D05042J | | 16 | | ALL |
| 771R | 22 | | PH | | 6-0 | 26-11-21 | D07984J | | 4 | | D04940J | | 1 | | ALL |
| 772R | 22 | | PH | | 6-0 | 26-11-21 | D07982J | | 4 | | D04952J | | 11 | | ALL |
| 773 | 20 | | PA | | 7-0 | 26-16-21 | D04952J | | 37 | | TB0104X | A006 | BJ | | ALL |
| 774R | 22 | | PH | | 7-0 | 26-11-21 | TB0106Y | A024 | BJ | | D04952J | | 12 | | ALL |
| 775R | 22 | | PH | | 7-0 | 26-11-21 | TB0096D | A025 | 2 | | D04952J | | 13 | | ALL |
| 776R | 22 | | PH | | 7-0 | 26-11-21 | TB0096D | A026 | 2 | | D04756J | | 13 | | ALL |
| 777R | 22 | | PH | | 7-0 | 26-11-21 | TB0096D | C024 | 2 | | D04952J | | 14 | | ALL |
| 778 | 20 | | PA | | 6-0 | 26-16-21 | TB0104X | D003 | BJ | | D04952J | | 38 | | ALL |
| 779R | 22 | | PH | | 6-0 | 26-11-22 | D07984J | | 5 | | D04940J | | 6 | | ALL |
| 780R | 22 | | PH | | 6-0 | 26-11-22 | D07982J | | 5 | | D04952J | | 16 | | ALL |
| 781R | 22 | | PH | | 6-0 | 26-11-11 | D07984J | | 1 | | D04938J | | 1 | | ALL |
| 782R | 22 | | PH | | 7-0 | 26-11-11 | D05042J | | 36 | | TB0096D | A027 | 2 | | ALL |
| 783R | 22 | | PH | | 1-0 | 26-11-11 | TB0096D | | C027 | 2 | TB0096D | C028 | 2 | | ALL |
| 784R | 22 | | PH | | 1-0 | 26-11-11 | TB0096D | | C028 | 2 | TB0096D | C029 | 2 | | ALL |
| 785R | 22 | | PH | | 7-0 | 26-11-21 | D04952J | | 36 | | TB0096D | A024 | 2 | | ALL |
| 786R | 22 | | PH | | 1-0 | 26-11-21 | TB0096D | | C024 | 2 | TB0096D | C025 | 2 | | ALL |
| 787R | 22 | | PH | | 1-0 | 26-11-21 | TB0096D | | C025 | 2 | TB0096D | C026 | 2 | | ALL |
| 788R | 22 | | PH | | 7-0 | 26-15-11 | D04952J | | 29 | | TB0096D | A013 | 2 | | ALL |
| 789R | 22 | | PH | | 7-0 | 26-15-11 | D04952J | | 33 | | TB0096D | A014 | 2 | | ALL |
| 790R | 22 | | PH | | 7-0 | 26-15-11 | D04952J | | 32 | | TB0096D | C013 | 2 | | ALL |
| 791R | 22 | | PH | | 1-0 | 26-15-11 | TB0096D | | C013 | 2 | TB0096D | C014 | 2 | | ALL |
| 792R | 22 | | PH | | 6-0 | 26-17-11 | D07984J | | 6 | | D04852J | | 6 | | ALL |
| 793R | 22 | | PH | | 6-0 | 26-17-11 | D07984J | | 7 | | D04852J | | 7 | | ALL |
| 794R | 22 | | PH | | 3-0 | 26-17-11 | D05784J | | 9 | | D04852J | | 10 | | ALL |
| 800R | 22 | | PH | | 6-0 | 26-18-31 | D04952J | | 42 | | TB0098X | A006 | BJ | | ALL |
| 801R | 20 | | PH | | 7-0 | 26-23-12 | D01928 | | 1 | | D04852J | | 19 | | 050-099 |

WIRE LIST

D280T132

91-21-11
 Section W0070
 Page 14
 Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | | | |
| 801R | 20 | | PH | 7-0 | 26-23-12 | D04852J | | 19 | | | | | TB0106Y | A023 | BJ | | 150-154 |
| 801R | 20 | | PH | 7-0 | 26-23-12 | D04852J | | 19 | | | | | D01928 | 1 | | | 155-199, 275-299 |
| 802R | 20 | | PH | 7-0 | 26-23-12 | D01928 | | 2 | | | | | D04852J | 20 | | | 050-099 |
| 802R | 20 | | PH | 7-0 | 26-23-12 | D04852J | | 20 | | | | | TB0106Y | C024 | BJ | | 150-154 |
| 802R | 20 | | PH | 7-0 | 26-23-12 | D04852J | | 20 | | | | | D01928 | 2 | | | 155-199, 275-299 |
| 803R | 20 | | PH | 6-0 | 26-21-11 | D01928 | | 3 | | | | | TB0106Y | A021 | BJ | | ALL |
| 804R | 20 | | PH | 6-0 | 26-21-11 | D01928 | | 4 | | | | | TB0106Y | A022 | BJ | | ALL |
| 805R | 20 | | PH | 7-0 | 26-21-11 | D01928 | | 5 | | | | | GD04424 | D.. | 2 | | ALL |
| 806R | 20 | | PH | 6-0 | 26-23-12 | D01928 | | 6 | | | | | TB0106Y | A020 | BJ | | ALL |
| 807R | 20 | | PH | 6-0 | 26-22-21 | D01928 | | 7 | | | | | TB0106Y | C023 | BJ | | ALL |
| 808R | 20 | | PH | 6-0 | 26-21-11 | D01928 | | 8 | | | | | D04952J | 3 | | | ALL |
| 809R | 20 | | PH | 6-0 | 26-21-11 | D01928 | | 9 | | | | | D04952J | 4 | | | ALL |
| 810R | 20 | | PH | 6-0 | 26-23-12 | D01928 | | 10 | | | | | D04952J | 5 | | | 050-099 |
| 810R | 20 | | PH | 7-0 | 26-23-12 | D04952J | | 5 | | | | | TB0106Y | A023 | BJ | | 150-154 |
| 810R | 20 | | PH | 7-0 | 26-23-12 | D04952J | | 5 | | | | | D01928 | 10 | | | 155-199, 275-299 |
| 811R | 20 | | PH | 6-0 | 26-23-12 | D01928 | | 11 | | | | | D04952J | 6 | | | 050-099 |
| 811R | 20 | | PH | 7-0 | 26-23-12 | D04952J | | 6 | | | | | TB0106Y | C024 | BJ | | 150-154 |
| 811R | 20 | | PH | 7-0 | 26-23-12 | D04952J | | 6 | | | | | D01928 | 11 | | | 155-199, 275-299 |
| 812R | 20 | | PH | 6-0 | 26-22-21 | D04952J | | 2 | | | | | D01928 | 12 | | | ALL |
| 813R | 20 | | PH | 6-0 | 26-22-21 | D01928 | | 13 | | | | | TB0106Y | C025 | BJ | | 275-299 |
| 814R | 20 | | PH | 7-0 | 26-22-21 | D01928 | | 14 | | | | | D04952J | 43 | | | 275-299 |
| 815R | 20 | | PH | 6-0 | 26-23-12 | D01928 | | 10 | | | | | TB0106Y | A023 | BJ | | 150-154 |
| 816R | 20 | | PH | 6-0 | 26-23-12 | D01928 | | 11 | | | | | TB0106Y | C024 | BJ | | 150-154 |
| 833R | 20 | | PH | 6-0 | 26-21-11 | D01930 | | 3 | | | | | TB0106Y | C021 | BJ | | ALL |
| 834R | 20 | | PH | 6-0 | 26-21-11 | D01930 | | 4 | | | | | TB0106Y | C022 | BJ | | ALL |
| 835R | 20 | | PH | 7-0 | 26-21-11 | D01930 | | 5 | | | | | GD04424 | D.. | 2 | | ALL |
| 836R | 20 | | PH | 6-0 | 26-23-11 | D01930 | | 6 | | | | | TB0106Y | C020 | BJ | | ALL |
| 838R | 20 | | PH | 6-0 | 26-21-11 | D01930 | | 8 | | | | | D05042J | 3 | | | ALL |
| 839R | 20 | | PH | 6-0 | 26-21-11 | D01930 | | 9 | | | | | D05042J | 4 | | | ALL |
| 840R | 20 | | PH | 6-0 | 26-23-11 | D01930 | | 10 | | | | | D05042J | 5 | | | ALL |
| 841R | 20 | | PH | 6-0 | 26-23-11 | D01930 | | 11 | | | | | D05042J | 6 | | | ALL |
| 845 | 22 | | PA | 2-0 | 33-16-17 | TB0068Y | | A019 | BJ | | | | TB0070Y | C021 | BJ | | 050-099, 155-199 |
| 845 | 22 | | PA | 3-0 | 33-16-17 | TB0068Y | | A019 | BJ | | | | TB0070Y | C021 | BJ | | 150-154 |
| 851 | 20 | | PA | 7-0 | 25-63-11 | D00636 | | | A | | | | GD00267 | S.. | 2 | | ALL |
| 852 | 20 | | PA | 12-0 | 25-63-11 | D00636 | | | B | | | | TB0096G | 16 | 2 | | ALL |
| 853 | 20 | | PA | 7-0 | 25-63-11 | D00636 | | | C | | | | GD00267 | D.. | 2 | | ALL |
| 854 | 20 | | PA | 15-0 | 25-63-11 | D00636 | | | D | | | | D08104J | 1 | | | ALL |
| 855 | 20 | | PA | 8-0 | 33-13-16 | D00636 | | | E | | | | TB0068H | 3 | 2 | | 050-099 |
| 855 | 20 | | PA | 7-0 | 33-13-16 | D00636 | | | E | | | | TB0068H | 3 | 2 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 15

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0070 | 286T0070 | | | P5-P61-S2-PILOT OVHD & RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 856 | 20 | | PA | | 7-0 | 33-13-16 | D00636 | | F | | GD00267 | A.. | 2 | | ALL |
| 863 | 22 | | PQ | SG | 7-0 | 33-16-17 | TB0068Y | C020 | BJ | | D02890 | | 3 | | ALL |
| 863Z | | | | SG | 0-0 | 33-16-17 | TB0068Y | | DED | | D02890 | | DED | | ALL |
| 864 | 22 | | PA | | 7-0 | 33-16-17 | TB0068Z | | 21 | BJ | D02890 | | 4 | | ALL |
| 866 | 22 | | PA | | 7-0 | 27-41-11 | D02890 | | 6 | | TB0068X | D010 | BJ | | ALL |
| 867 | 22 | | PA | | 7-0 | 27-61-12 | D02890 | | 7 | | TB0068X | A009 | BJ | | ALL |
| 868 | 22 | | PA | | 7-0 | 27-11-12 | D02890 | | 8 | | TB0068X | C009 | BJ | | ALL |
| 869 | 22 | | PA | | 7-0 | 27-41-11 | D02890 | | 9 | | TB0068X | C010 | BJ | | ALL |
| 870 | 22 | | PA | | 7-0 | 27-21-12 | D02890 | | 10 | | TB0068X | D009 | BJ | | ALL |
| 875 | 22 | | PA | | 12-0 | 32-42-11 | D02890 | | 15 | | TB0106Y | C017 | BJ | | ALL |
| 877R | 20 | | PH | | 10-0 | 26-22-21 | D04006P | | 28 | | TB0106Y | C025 | BJ | | 275-299 |
| 879R | 20 | | PH | | 7-0 | 26-22-21 | D04952J | | 30 | | TB0106Y | C025 | BJ | | 275-299 |
| 880R | 20 | | PH | | 7-0 | 26-23-12 | D04852J | | 18 | | TB0106Y | A020 | BJ | | 150-199, 275-299 |
| 881R | 20 | | PH | | 10-0 | 26-21-11 | D04008P | | 29 | | TB0106Y | A022 | BJ | | ALL |
| 882R | 20 | | PH | | 7-0 | 26-21-11 | D04952J | | 10 | | TB0106Y | A022 | BJ | | ALL |
| 883R | 20 | | PH | | 10-0 | 26-21-11 | D04008P | | 30 | | TB0106Y | A021 | BJ | | ALL |
| 884R | 20 | | PH | | 7-0 | 26-21-11 | D04952J | | 19 | | TB0106Y | A021 | BJ | | ALL |
| 885R | 20 | | PH | | 10-0 | 26-23-11 | TB0106Y | C020 | BJ | | D04008P | | 31 | | ALL |
| 886R | 20 | | PH | | 7-0 | 26-23-11 | TB0106Y | C020 | BJ | | D05042J | | 26 | | ALL |
| 887R | 20 | | PH | | 10-0 | 26-22-21 | D04010P | | 29 | | TB0106Y | C023 | BJ | | ALL |
| 888R | 20 | | PH | | 7-0 | 26-22-21 | D04952J | | 1 | | TB0106Y | C023 | BJ | | ALL |
| 889R | 20 | | PH | | 7-0 | 26-22-21 | D04952J | | 20 | | TB0106Y | C023 | BJ | | ALL |
| 891R | 20 | | PH | | 10-0 | 26-21-11 | D04006P | | 29 | | TB0106Y | C022 | BJ | | ALL |
| 892R | 20 | | PH | | 7-0 | 26-21-11 | D05042J | | 10 | | TB0106Y | C022 | BJ | | ALL |
| 893R | 20 | | PH | | 10-0 | 26-21-11 | D04006P | | 30 | | TB0106Y | C021 | BJ | | ALL |
| 894R | 20 | | PH | | 7-0 | 26-21-11 | D05042J | | 19 | | TB0106Y | C021 | BJ | | ALL |
| 895R | 20 | | PH | | 10-0 | 26-23-12 | TB0106Y | A020 | BJ | | D04006P | | 31 | | ALL |
| 896R | 20 | | PH | | 7-0 | 26-23-12 | TB0106Y | A020 | BJ | | D04952J | | 26 | | 050-099 |
| 896R | 20 | | PH | | 7-0 | 26-23-12 | D04952J | | 26 | | TB0106Y | A020 | BJ | | 150-199, 275-299 |
| 897R | 24 | | PP | | 7-0 | 26-16-11 | D07980J | | 7 | | D05042J | | 7 | | ALL |
| 898R | 24 | | PP | | 6-0 | 26-16-11 | D07982J | | 7 | | D04952J | | 7 | | ALL |
| A-A | | | | | 0-0 | 33-11-16 | L00673 | | WHT | | SP02318 | | 9 | | ALL |
| B-A | | | | | 0-0 | 33-11-16 | L00674 | | WHT | | SP02318 | | 9 | | ALL |
| W0072 | 286T0072 | | | P70 FWD LEFT OFF-WING ESCAPE SYSTEM SWITCH PNL | | | | | | | | | | | |
| 001 | 22 | | PA | | 2-0 | 25-65-11 | D06402J | | 1 | | S00530 | | 5 | C | 050-099 |
| 001 | 22 | | PA | | 2-0 | 25-65-11 | D06402J | | 1 | | S00624 | | 5 | C | 150-199, 275-299 |
| 002 | 22 | | PA | | 2-0 | 25-65-11 | D06402J | | 2 | | S00530 | | 1 | C | 050-099 |
| 002 | 22 | | PA | | 2-0 | 25-65-11 | D06402J | | 2 | | S00624 | | 1 | C | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 16

Jan 21/2005



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|--------|--------|---|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0072 | 286T0072 | | | P70 FWD LEFT OFF-WING ESCAPE SYSTEM SWITCH PNL (continued) | | | | | | | | | | | | | |
| 003 | 20 | | PA | 2-0 | 25-65-11 | D06402J | | 3 | | | | | S00528 | 5 | C | | 050-099 |
| 003 | 20 | | PA | 2-0 | 25-65-11 | D06402J | | 3 | | | | | S00620 | 5 | C | | 150-199, 275-299 |
| 004 | 18 | | PA | 2-0 | 25-65-11 | D06402J | | 4 | | | | | S00528 | 1 | C | | 050-099 |
| 004 | 18 | | PA | 2-0 | 25-65-11 | D06402J | | 4 | | | | | S00620 | 1 | C | | 150-199, 275-299 |
| 005 | 22 | | PA | 2-0 | 25-65-11 | D06402J | | 5 | | | | | S00532 | 1 | C | | 050-099 |
| 005 | 22 | | PA | 2-0 | 25-65-11 | D06402J | | 5 | | | | | S00628 | 1 | C | | 150-199, 275-299 |
| 006 | 20 | | PA | 2-0 | 25-65-11 | D06402J | | 6 | | | | | S00532 | 2 | C | | 050-099 |
| 006 | 20 | | PA | 2-0 | 25-65-11 | D06402J | | 6 | | | | | S00628 | 2 | C | | 150-199, 275-299 |
| 007 | 18 | | PA | 2-0 | 25-65-11 | D06402J | | 7 | | | | | S00528 | 4 | C | | 050-099 |
| 007 | 18 | | PA | 2-0 | 25-65-11 | D06402J | | 7 | | | | | S00620 | 4 | C | | 150-199, 275-299 |
| 008 | 20 | | PA | 2-0 | 25-65-11 | D06402J | | 8 | | | | | S00532 | 5 | C | | 050-099 |
| 008 | 20 | | PA | 2-0 | 25-65-11 | D06402J | | 8 | | | | | S00628 | 5 | C | | 150-199, 275-299 |
| 010 | 18 | | PA | 2-0 | 25-65-11 | D06402J | | 10 | | | | | S00624 | 6 | C | * | 150-199, 275-299 |
| 01A | 22 | | PA | 2-0 | 25-65-11 | S00530 | | 6 | C | | | | S00530 | 2 | C | * | 050-099 |
| 01A | 20 | | PA | 1-0 | 25-65-11 | S00624 | | 6 | C | * | | | S00624 | 2 | C | * | 150-199, 275-299 |
| 01B | 20 | | PA | 1-0 | 25-65-11 | S00528 | | 2 | C | | | | S00530 | 2 | C | * | 050-099 |
| 01B | 20 | | PA | 1-0 | 25-65-11 | S00620 | | 2 | C | | | | S00624 | 2 | C | * | 150-199, 275-299 |
| 01C | 20 | | PA | 1-0 | 25-65-11 | S00530 | | 3 | C | * | | | S00532 | 6 | C | | 050-099 |
| 01C | 20 | | PA | 1-0 | 25-65-11 | S00628 | | 3 | C | * | | | S00628 | 6 | C | | 150-199, 275-299 |
| 01D | 20 | | PA | 1-0 | 25-65-11 | S00530 | | 3 | C | * | | | S00532 | 3 | C | | 050-099 |
| 01D | 20 | | PA | 1-0 | 25-65-11 | S00628 | | 3 | C | * | | | S00624 | 3 | C | | 150-199, 275-299 |
| W0074 | 286T0074 | | | P72 AFT LEFT OFF-WING ESCAPE SYSTEM SWITCH PNL | | | | | | | | | | | | | |
| 001 | 22 | | PA | 2-0 | 25-65-11 | D06404J | | 1 | | | | | S00622 | 5 | C | * | 150-199, 275-299 |
| 002 | 22 | | PA | 2-0 | 25-65-11 | D06404J | | 2 | | | | | S00622 | 1 | C | | 150-199, 275-299 |
| 004 | 18 | | PA | 2-0 | 25-65-11 | D06404J | | 4 | DL | | | | S00618 | 1 | C | | 150-199, 275-299 |
| 005 | 22 | | PA | 2-0 | 25-65-11 | D06404J | | 5 | | | | | S00626 | 4 | C | | 150-199, 275-299 |
| 006 | 20 | | PA | 2-0 | 25-65-11 | D06404J | | 6 | | | | | S00626 | 2 | C | * | 150-199, 275-299 |
| 007 | 18 | | PA | 2-0 | 25-65-11 | D06404J | | 7 | DL | | | | S00618 | 4 | C | | 150-199, 275-299 |
| 008 | 20 | | PA | 2-0 | 25-65-11 | D06404J | | 8 | | | | | S00626 | 5 | C | * | 150-199, 275-299 |
| 009 | 20 | | PA | 2-0 | 25-65-11 | D06404J | | 9 | | | | | S00622 | 5 | C | * | 150-199, 275-299 |
| 010 | 18 | | PA | 2-0 | 25-65-11 | D06404J | | 10 | DL | | | | S00622 | 2 | C | * | 150-199, 275-299 |
| 012 | 22 | | PA | 2-0 | 25-65-11 | D06404J | | 12 | | | | | S00622 | 4 | C | | 150-199, 275-299 |
| 014 | 18 | | PA | 2-0 | 25-65-11 | D06404J | | 14 | DL | | | | S00618 | 2 | C | | 150-199, 275-299 |
| 016 | 18 | | PA | 2-0 | 25-65-11 | D06404J | | 16 | DL | | | | S00618 | 5 | C | | 150-199, 275-299 |
| 01A | 22 | | PA | 1-0 | 25-65-11 | S00622 | | 6 | C | | | | S00622 | 2 | C | * | 150-199, 275-299 |
| 01C | 20 | | PA | 1-0 | 25-65-11 | S00626 | | 6 | C | | | | S00626 | 3 | C | * | 150-199, 275-299 |
| 01D | 20 | | PA | 1-0 | 25-65-11 | S00622 | | 3 | C | | | | S00626 | 3 | C | * | 150-199, 275-299 |
| 020 | 18 | | PA | 2-0 | 25-65-11 | D06404J | | 20 | DL | | | | S00626 | 5 | C | * | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0070

Page 17

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|--------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0074 | 286T0074 | | | P72 AFT LEFT OFF-WING ESCAPE SYSTEM SWITCH PNL (continued) | | | | | | | | | | | |
| 024 | 18 | | PA | | 2-0 | 25-65-11 | D06404J | 24 | DL | | S00626 | 2 | C | * | 150-199, 275-299 |
| W0076 | 286T0076 | | | P71 FWD RIGHT OFF-WING ESCAPE SYSTEM SWITCH PNL | | | | | | | | | | | |
| 001 | 22 | | PA | | 2-0 | 25-65-12 | D06406J | 1 | | | S00531 | 5 | C | | 050-099 |
| 001 | 22 | | PA | | 2-0 | 25-65-12 | D06406J | 1 | | | S00623 | 5 | C | | 150-199, 275-299 |
| 002 | 22 | | PA | | 2-0 | 25-65-12 | D06406J | 2 | | | S00531 | 1 | C | | 050-099 |
| 002 | 22 | | PA | | 2-0 | 25-65-12 | D06406J | 2 | | | S00623 | 1 | C | | 150-199, 275-299 |
| 003 | 20 | | PA | | 2-0 | 25-65-12 | D06406J | 3 | | | S00529 | 5 | C | | 050-099 |
| 003 | 20 | | PA | | 2-0 | 25-65-12 | D06406J | 3 | | | S00619 | 5 | C | | 150-199, 275-299 |
| 004 | 18 | | PA | | 2-0 | 25-65-12 | D06406J | 4 | | | S00529 | 1 | C | | 050-099 |
| 004 | 18 | | PA | | 2-0 | 25-65-12 | D06406J | 4 | | | S00619 | 1 | C | | 150-199, 275-299 |
| 005 | 22 | | PA | | 2-0 | 25-65-12 | D06406J | 5 | | | S00533 | 1 | C | | 050-099 |
| 005 | 22 | | PA | | 2-0 | 25-65-12 | D06406J | 5 | | | S00627 | 1 | C | | 150-199, 275-299 |
| 006 | 20 | | PA | | 2-0 | 25-65-12 | D06406J | 6 | | | S00533 | 2 | C | | 050-099 |
| 006 | 20 | | PA | | 2-0 | 25-65-12 | D06406J | 6 | | | S00627 | 2 | C | | 150-199, 275-299 |
| 007 | 18 | | PA | | 2-0 | 25-65-12 | D06406J | 7 | | | S00529 | 4 | C | | 050-099 |
| 007 | 18 | | PA | | 2-0 | 25-65-12 | D06406J | 7 | | | S00619 | 4 | C | | 150-199, 275-299 |
| 008 | 20 | | PA | | 2-0 | 25-65-12 | D06406J | 8 | | | S00533 | 5 | C | | 050-099 |
| 008 | 20 | | PA | | 2-0 | 25-65-12 | D06406J | 8 | | | S00627 | 5 | C | | 150-199, 275-299 |
| 010 | 18 | | PA | | 2-0 | 25-65-12 | D06406J | 10 | | | S00623 | 6 | C | * | 150-199, 275-299 |
| 01A | 22 | | PA | | 1-0 | 25-65-12 | S00531 | 6 | C | | S00531 | 2 | C | * | 050-099 |
| 01A | 20 | | PA | | 1-0 | 25-65-12 | S00623 | 6 | C | * | S00623 | 2 | C | * | 150-199, 275-299 |
| 01B | 20 | | PA | | 1-0 | 25-65-12 | S00529 | 2 | C | | S00531 | 2 | C | * | 050-099 |
| 01B | 20 | | PA | | 1-0 | 25-65-12 | S00619 | 2 | C | | S00623 | 2 | C | * | 150-199, 275-299 |
| 01C | 20 | | PA | | 1-0 | 25-65-12 | S00531 | 3 | C | * | S00533 | 6 | C | | 050-099 |
| 01C | 20 | | PA | | 1-0 | 25-65-12 | S00627 | 3 | C | * | S00627 | 6 | C | | 150-199, 275-299 |
| 01D | 20 | | PA | | 1-0 | 25-65-12 | S00531 | 3 | C | * | S00533 | 3 | C | | 050-099 |
| 01D | 20 | | PA | | 1-0 | 25-65-12 | S00627 | 3 | C | * | S00623 | 3 | C | | 150-199, 275-299 |
| W0078 | 286T0078 | | | P73 AFT RIGHT OFF-WING ESCAPE SYSTEM SWITCH PNL | | | | | | | | | | | |
| 001 | 22 | | PA | | 2-0 | 25-65-12 | D06408J | 1 | | | S00621 | 5 | C | * | 150-199, 275-299 |
| 002 | 22 | | PA | | 2-0 | 25-65-12 | D06408J | 2 | | | S00621 | 1 | C | | 150-199, 275-299 |
| 004 | 18 | | PA | | 2-0 | 25-65-12 | D06408J | 4 | DL | | S00617 | 1 | C | | 150-199, 275-299 |
| 005 | 22 | | PA | | 2-0 | 25-65-12 | D06408J | 5 | | | S00625 | 4 | C | | 150-199, 275-299 |
| 006 | 20 | | PA | | 2-0 | 25-65-12 | D06408J | 6 | | | S00625 | 2 | C | * | 150-199, 275-299 |
| 007 | 18 | | PA | | 2-0 | 25-65-12 | D06408J | 7 | DL | | S00617 | 4 | C | | 150-199, 275-299 |
| 008 | 20 | | PA | | 2-0 | 25-65-12 | D06408J | 8 | | | S00625 | 5 | C | * | 150-199, 275-299 |
| 009 | 20 | | PA | | 2-0 | 25-65-12 | D06408J | 9 | | | S00621 | 5 | C | * | 150-199, 275-299 |
| 010 | 18 | | PA | | 2-0 | 25-65-12 | D06408J | 10 | DL | | S00621 | 2 | C | * | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11
Section W0070
Page 18
Jan 21/2005



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0078 | 286T0078 | | | P73 AFT RIGHT OFF-WING ESCAPE SYSTEM SWITCH PNL (continued) | | | | | | | | | | |
| 012 | 22 | | PA | 2-0 | 25-65-12 | D06408J | 12 | | | S00621 | 4 | C | | 150-199, 275-299 |
| 014 | 18 | | PA | 2-0 | 25-65-12 | D06408J | 14 | DL | | S00617 | 2 | C | | 150-199, 275-299 |
| 016 | 18 | | PA | 2-0 | 25-65-12 | D06408J | 16 | DL | | S00617 | 5 | C | | 150-199, 275-299 |
| 01A | 22 | | PA | 1-0 | 25-65-12 | S00621 | 6 | C | | S00621 | 2 | C | * | 150-199, 275-299 |
| 01C | 20 | | PA | 1-0 | 25-65-12 | S00625 | 6 | C | | S00625 | 3 | C | * | 150-199, 275-299 |
| 01D | 20 | | PA | 1-0 | 25-65-12 | S00621 | 3 | C | | S00625 | 3 | C | * | 150-199, 275-299 |
| 020 | 18 | | PA | 2-0 | 25-65-12 | D06408J | 20 | DL | | S00625 | 5 | C | * | 150-199, 275-299 |
| 024 | 18 | | PA | 2-0 | 25-65-12 | D06408J | 24 | DL | | S00625 | 2 | C | * | 150-199, 275-299 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----|------------------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0082 | 286T0082 | | | | SHELF E3-1 LEFT | | | | | | | | | | | | |
| 001 | 20 | PQ | | AR | 5-0 | 21-53-11 | D08040P | | 1 | | | | D00958C | 2 | | | ALL |
| 001Z | | | | AR | 0-0 | 21-53-11 | D08040P | | DED | | | | D00958C | DED | | | ALL |
| 002 | 24 | PK | | | 5-0 | 21-53-11 | D08040P | | 2 | | | | D00958B | A15 | | | ALL |
| 003 | 24 | PK | | | 5-0 | 21-53-11 | D08040P | | 3 | | | | D00958B | A13 | | | ALL |
| 004 | 24 | PK | | | 5-0 | 21-53-11 | D08040P | | 4 | | | | D00958B | B15 | | | ALL |
| 005 | 24 | PK | | | 5-0 | 21-53-11 | D08040P | | 5 | | | | D00958B | B13 | | | ALL |
| 006 | 24 | PK | | | 5-0 | 21-53-11 | D08040P | | 6 | | | | D00958B | C15 | | | ALL |
| 007 | 24 | PK | | | 5-0 | 21-53-11 | D08040P | | 7 | | | | D00958B | C13 | | | ALL |
| 008 | 20 | PA | | | 3-0 | 21-53-11 | D00958C | | 4 | | | | GDX0001 | A.. | 2 | | ALL |
| 021 | 22 | PA | | | 3-0 | 21-51-12 | D00958A | | C15 | | | | GDX0001 | D.. | 2 | | ALL |
| 028 | 24 | PK | | | 3-0 | 21-51-12 | D00958B | | B05 | | | | D00958B | B06 | | | 050-099 |
| 028 | 24 | PK | | | 1-0 | 21-51-12 | D00958B | | B05 | | | | D00958B | B06 | | | 150-199, 275-299 |
| 069 | 24 | PK | | | 5-0 | 21-61-51 | D08092P | | 27 | | | | TB0164F | C010 | 2 | | ALL |
| 070 | 24 | PK | | | 5-0 | 36-23-11 | D04502P | | 6 | | | | TB0168X | A001 | BJ | | 050-099, 156-162, 166-199, 277-299 |
| 070 | 24 | PK | | | 5-0 | 36-23-11 | D04502P | | 6 | | | | TB0168F | A001 | 2 | | 150-155, 163-165, 275-276 |
| 071 | 24 | PK | | | 5-0 | 36-23-11 | D04502P | | 7 | | | | TB0168X | C001 | BJ | | 050-099, 156-162, 166-199, 277-299 |
| 071 | 24 | PK | | | 5-0 | 36-23-11 | D04502P | | 7 | | | | TB0168F | C001 | 2 | | 150-155, 163-165, 275-276 |
| 072 | 24 | PK | | | 5-0 | 36-23-11 | D04502P | | 8 | | | | TB0168X | B001 | BJ | | 050-099, 156-162, 166-199, 277-299 |
| 072 | 24 | PK | | | 5-0 | 36-23-11 | D04502P | | 8 | | | | TB0168F | A002 | 2 | | 150-155, 163-165, 275-276 |
| 073 | 22 | PA | | | 4-0 | 36-23-11 | D04502P | | 9 | | | | GDX0003 | D.. | 2 | | ALL |
| 074 | 24 | PK | | | 5-0 | 36-23-11 | D04502P | | 10 | | | | TB0168X | D001 | BJ | | 050-099, 156-162, 166-199, 277-299 |
| 074 | 24 | PK | | | 5-0 | 36-23-11 | D04502P | | 10 | | | | TB0168F | C002 | 2 | | 150-155, 163-165, 275-276 |
| 075 | 24 | PK | | | 4-0 | 36-23-11 | D08092P | | 23 | | | | TB0168X | A003 | BJ | | 050-099, 156-162, 166-199, 277-299 |
| 075 | 24 | PK | | | 4-0 | 36-23-11 | D08092P | | 23 | | | | TB0168F | A005 | 2 | | 150-155, 163-165, 275-276 |
| 076 | 24 | PK | | | 4-0 | 36-23-11 | D08092P | | 29 | | | | TB0168X | C003 | BJ | | 050-099, 156-162, 166-199, 277-299 |
| 076 | 24 | PK | | | 4-0 | 36-23-11 | D08092P | | 29 | | | | TB0168F | C005 | 2 | | 150-155, 163-165, 275-276 |

WIRE LIST
D280T132

91-21-11
Section W0080
Page 1
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0082 | 286T0082 | | | SHELF E3-1 LEFT (continued) | | | | | | | | | | | | |
| 077 | 24 | | PK | 4-0 | 36-23-11 | D08092P | | 28 | | | | TB0168X | B003 | BJ | | 050-099, 156-162, 166-199, 277-299 |
| 077 | 24 | | PK | 4-0 | 36-23-11 | D08092P | | 28 | | | | TB0168F | A006 | 2 | | 150-155, 163-165, 275-276 |
| 078 | 24 | | PK | 4-0 | 36-23-11 | D08092P | | 30 | | | | TB0168X | D003 | BJ | | 050-099, 156-162, 166-199, 277-299 |
| 078 | 24 | | PK | 4-0 | 36-23-11 | D08092P | | 30 | | | | TB0168F | C006 | 2 | | 150-155, 163-165, 275-276 |
| 079 | 24 | | PK | 4-0 | 36-23-11 | D05782P | | 2 | | | | TB0168F | A007 | 2 | | ALL |
| 080 | 24 | | PK | 4-0 | 36-23-11 | D05782P | | 3 | | | | TB0168F | C007 | 2 | | ALL |
| 081 | 24 | | PK | 4-0 | 36-23-11 | D05782P | | 7 | | | | TB0168F | A009 | 2 | | ALL |
| 082 | 24 | | PK | 4-0 | 36-23-11 | D05782P | | 8 | | | | TB0168F | A008 | 2 | | ALL |
| 083 | 18 | | PA | 4-0 | 36-11-51 | D08092P | | 24 | DL | | | TB0168G | 10 | 2 | | ALL |
| 085 | 18 | | PA | 4-0 | 36-11-51 | D08092P | | 32 | DL | | | TB0168G | 11 | 2 | | ALL |
| 087 | 18 | | PA | 4-0 | 36-11-51 | D08092P | | 34 | DL | | | D08092P | 40 | DL | | 150-154, 275 |
| 090 | 24 | | PK | 4-0 | 36-11-61 | D05782P | | 12 | | | | TB0168G | 13 | 2 | | ALL |
| 091 | 24 | | PK | 4-0 | 36-11-61 | D05782P | | 6 | | | | TB0168G | 13 | 2 | | ALL |
| 092 | 18 | | PA | 4-0 | 36-11-61 | D05782P | | 13 | DK | | | TB0168G | 14 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 093 | 18 | | PA | 4-0 | 36-11-61 | D05782P | | 5 | DK | | | TB0168G | 14 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 093 | 18 | | PA | 4-0 | 36-11-61 | D05782P | | 14 | DK | | | TB0168G | 14 | 2 | | 156, 166 |
| 095 | 24 | | PK | 4-0 | 36-11-61 | D05782P | | 11 | | | | TB0168G | 15 | 2 | | ALL |
| 096 | 24 | | PK | 5-0 | 21-61-11 | D05686P | | 13 | | | | TB0166X | C006 | BJ | | ALL |
| 097 | 24 | | PK | 5-0 | 21-61-11 | D05686P | | 14 | | | | TB0166X | D006 | BJ | | ALL |
| 098 | 24 | | PK | 5-0 | 21-61-21 | D05686P | | 19 | | | | TB0166X | D007 | BJ | | ALL |
| 099 | 24 | | PK | 5-0 | 21-61-21 | D05686P | | 18 | | | | TB0166X | C007 | BJ | | ALL |
| 100 | 24 | | PK | 5-0 | 21-61-31 | D05686P | | 23 | | | | TB0166F | A008 | 2 | | ALL |
| 101 | 24 | | PK | 5-0 | 21-61-31 | D05686P | | 24 | | | | TB0166F | C008 | 2 | | ALL |
| 102 | 24 | | PV | 4-0 | 36-23-11 | D04502P | | 11 | | | | TB0168F | C009 | 2 | | ALL |
| 102Z | | | | 0-0 | 36-23-11 | D04502P | | | DED | | | TB0168F | DED | | | ALL |
| 104 | 24 | | PV | 4-0 | 21-52-41 | D08040P | | 8 | | | | D01174B | B14 | | | ALL |
| 104Z | | | | 0-0 | 21-52-41 | D08040P | | | DED | | | D01174B | DED | | | ALL |
| 105 | 22 | | PA | 4-0 | 21-52-41 | GDX0001 | | A.. | 2 | | | D01174B | A15 | | | ALL |
| 106 | 22 | | PQ | 4-0 | 21-52-41 | GDX0001 | | S.. | 2 | | | D01174A | D15 | | | ALL |
| 106Z | | | | 0-0 | 21-52-41 | GDX0001 | | | DED | | | D01174A | DED | | | ALL |
| 107 | 20 | | PA | 5-0 | 36-11-51 | D08092P | | 38 | | | | GDX0001 | D.. | 2 | | ALL |
| 108 | 20 | | PA | 4-0 | 36-11-51 | D08092P | | 39 | | | | GDX0003 | D.. | 2 | | ALL |
| 112 | 14 | | PA | 1-0 | 21-53-11 | D00958C | | 3 | | | | SM00001 | | W | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0080

Page 2

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0082 | 286T0082 | | | SHELF E3-1 LEFT (continued) | | | | | | | | | | | |
| 113 | 24 | | PK | | 5-0 | 21-53-11 | D08040P | | | 9 | D00958B | D07 | | | ALL |
| 116 | 24 | | PK | | 5-0 | 21-51-11 | D00958B | | | C07 | D04502P | 23 | | | ALL |
| 117 | 22 | | PA | | 5-0 | 21-51-11 | D00958B | | | C05 | D04502P | 22 | | | ALL |
| 125 | 20 | | PA | | 0-6 | 21-53-11 | SM00001 | | W | | GDX0001 | S.. | 2 | | ALL |
| 126 | 24 | | PK | | 5-0 | 21-51-21 | D04502P | | | 26 | TB0170F | C007 | 2 | | 150-199, 275-299 |
| 127 | 24 | | PK | | 5-0 | 21-51-21 | D04502P | | | 27 | TB0170F | A008 | 2 | | 150-199, 275-299 |
| 128 | 24 | | PK | | 2-0 | 21-51-11 | D00958B | | | B03 | D00958B | B04 | | | 150-199, 275-299 |
| 130 | 24 | | PK | | 5-0 | 21-51-11 | D04500P | | | 51 | D00958B | B09 | | | ALL |
| 131 | 24 | | PK | | 4-0 | 36-23-11 | D05782P | | | 10 | TB0166F | A009 | 2 | | 050-099 |
| 131 | 24 | | PK | | 5-0 | 36-23-11 | D05782P | | | 10 | TB0166F | A009 | 2 | | 150-199, 275-299 |
| 132 | 24 | | PK | | 4-0 | 36-23-11 | D05782P | | | 24 | TB0166F | C009 | 2 | | 050-099 |
| 132 | 24 | | PK | | 5-0 | 36-23-11 | D05782P | | | 24 | TB0166F | C009 | 2 | | 150-199, 275-299 |
| 133 | 24 | | PK | | 5-0 | 21-61-41 | D05686P | | | 31 | TB0164F | C008 | 2 | | ALL |
| 134 | 24 | | PK | | 5-0 | 21-61-41 | D05686P | | | 34 | TB0164F | A008 | 2 | | ALL |
| 135 | 24 | | PK | | 3-0 | 21-51-11 | D00958B | | | B11 | TB0168X | A017 | BJ | | 150-199, 275-299 |
| 136 | 24 | | PK | | 3-0 | 21-51-11 | D00958B | | | B12 | TB0168X | B017 | BJ | | 150-199, 275-299 |
| 144 | 24 | | PK | | 5-0 | 21-61-11 | D05686P | | | 48 | TB0166X | A006 | BJ | | ALL |
| 145 | 24 | | PK | | 5-0 | 21-61-11 | D05686P | | | 49 | TB0166X | B006 | BJ | | ALL |
| 146 | 24 | | PK | | 5-0 | 21-61-21 | D05686P | | | 50 | TB0166X | A007 | BJ | | ALL |
| 147 | 24 | | PK | | 5-0 | 21-61-21 | D05686P | | | 51 | TB0166X | B007 | BJ | | ALL |
| 148 | 24 | | PK | | 5-0 | 21-61-31 | D05686P | | | 52 | TB0166X | A005 | BJ | | ALL |
| 149 | 24 | | PK | | 5-0 | 21-61-31 | D05686P | | | 53 | TB0166X | B005 | BJ | | ALL |
| 150 | 24 | | PK | | 5-0 | 21-61-41 | D05686P | | | 54 | TB0164X | A007 | BJ | | ALL |
| 151 | 24 | | PK | | 5-0 | 21-61-41 | D05686P | | | 55 | TB0164X | B007 | BJ | | ALL |
| 153 | 22 | | PA | | 5-0 | 36-23-11 | D05782P | | | 9 | TB0166X | D005 | BJ | | ALL |
| 154 | 22 | | PA | | 5-0 | 36-23-11 | D05782P | | | 16 | TB0166X | C005 | BJ | | ALL |
| 161 | 24 | | PK | | 6-0 | 36-23-11 | D08092P | | | 36 | TB0168X | A006 | BJ | | 050-099, 162 |
| 161 | 24 | | PK | | 4-0 | 36-23-11 | D08092P | | | 36 | TB0168X | A006 | BJ | | 156-157, 166-199, 277-299 |
| 164 | 24 | | PK | | 6-0 | 36-23-11 | D08092P | | | 25 | TB0168X | C004 | BJ | | 050-099, 162 |
| 164 | 24 | | PK | | 4-0 | 36-23-11 | D08092P | | | 25 | TB0168X | C004 | BJ | | 156-157, 166-199, 277-299 |
| 165 | 24 | | PK | | 6-0 | 36-23-11 | D08092P | | | 26 | TB0168X | D004 | BJ | | 050-099, 162 |
| 165 | 24 | | PK | | 4-0 | 36-23-11 | D08092P | | | 26 | TB0168X | D004 | BJ | | 156-157, 166-199, 277-299 |
| 166 | 24 | | PK | | 6-0 | 36-23-11 | D08092P | | | 31 | TB0168X | A005 | BJ | | 050-099, 162 |
| 166 | 24 | | PK | | 4-0 | 36-23-11 | D08092P | | | 31 | TB0168X | A005 | BJ | | 156-157, 166-199, 277-299 |
| 167 | 22 | | PA | | 6-0 | 36-23-11 | D08092P | | | 5 | TB0168X | B005 | BJ | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0080
Page 3
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0082 | 286T0082 | | | SHELF E3-1 LEFT (continued) | | | | | | | | | | | | | | |
| 167 | 24 | | PK | 4-0 | 36-23-11 | D05782P | | | | 5 | | | | TB0168X | B005 | BJ | | 156, 166 |
| 167 | 22 | | PA | 4-0 | 36-23-11 | D05782P | | | | 5 | | | | TB0168X | B005 | BJ | | 157, 167-199, 277-299 |
| 167 | 22 | | PA | 6-0 | 36-23-11 | D05782P | | | | 14 | | | | TB0168X | B005 | BJ | | 162 |
| 168 | 22 | | PA | 6-0 | 36-23-11 | D08092P | | | | 7 | | | | TB0168X | C005 | BJ | | 050-099 |
| 168 | 22 | | PA | 4-0 | 36-23-11 | D05782P | | | | 1 | | | | TB0168X | C005 | BJ | | 156-157, 166-199, 277-299 |
| 168 | 22 | | PA | 6-0 | 36-23-11 | D05782P | | | | 1 | | | | TB0168X | C005 | BJ | | 162 |
| 169 | 22 | | PA | 6-0 | 36-23-11 | D08092P | | | | 4 | | | | TB0168X | D005 | BJ | | 050-099 |
| 169 | 22 | | PA | 4-0 | 36-23-11 | D05782P | | | | 4 | | | | TB0168X | D005 | BJ | | 156-157, 166-199, 277-299 |
| 169 | 22 | | PA | 6-0 | 36-23-11 | D05782P | | | | 4 | | | | TB0168X | D005 | BJ | | 162 |
| 201B | 24 | | PL C | 5-0 | 21-51-12 | D04500P | | | | 13 | | | | D00958B | D06 | | | ALL |
| 201R | 24 | | PL C | 0-0 | 21-51-12 | D04500P | | | | 14 | | | | D00958B | D05 | | | ALL |
| 202B | 22 | | PB D | 5-0 | 21-51-12 | D04500P | | | | 15 | | | | D00958A | B04 | | | ALL |
| 202R | 22 | | PB D | 0-0 | 21-51-12 | D04500P | | | | 16 | | | | D00958A | B05 | | | ALL |
| 203B | 22 | | PB E | 5-0 | 21-51-12 | D08092P | | | | 1 | | | | D00958A | C04 | | | ALL |
| 203R | 22 | | PB E | 0-0 | 21-51-12 | D08092P | | | | 2 | | | | D00958A | C05 | | | ALL |
| 204B | 22 | | PB F | 3-0 | 21-51-12 | TB0166Y | | | | C011 | BJ | | | D00958A | A04 | | | 050-099, 151-199, 275-299 |
| 204B | 22 | | PB F | 5-0 | 21-51-12 | D04500P | | | | 20 | | | | D00958A | A04 | | | 150 |
| 204R | 22 | | PB F | 0-0 | 21-51-12 | TB0166Y | | | | C012 | BJ | | | D00958A | A05 | | | 050-099, 151-199, 275-299 |
| 204R | 22 | | PB F | 0-0 | 21-51-12 | D04500P | | | | 19 | | | | D00958A | A05 | | | 150 |
| 205B | 22 | | PB G | 5-0 | 21-51-12 | D04500P | | | | 22 | | | | D00958A | D04 | | | ALL |
| 205R | 22 | | PB G | 0-0 | 21-51-12 | D04500P | | | | 21 | | | | D00958A | D05 | | | ALL |
| 207B | 24 | | PL O | 5-0 | 21-61-11 | D08092P | | | | 17 | | | | TB0164F | C001 | 2 | | ALL |
| 207R | 24 | | PL O | 0-0 | 21-61-11 | D08092P | | | | 18 | | | | TB0164F | A001 | 2 | | ALL |
| 208B | 24 | | PL P | 5-0 | 21-61-11 | D08092P | | | | 15 | | | | TB0164F | C002 | 2 | | ALL |
| 208R | 24 | | PL P | 0-0 | 21-61-11 | D08092P | | | | 16 | | | | TB0164F | A002 | 2 | | ALL |
| 209B | 24 | | PL S | 5-0 | 21-61-21 | D08092P | | | | 19 | | | | TB0164X | A006 | BJ | | ALL |
| 209R | 24 | | PL S | 0-0 | 21-61-21 | D08092P | | | | 20 | | | | TB0164X | B006 | BJ | | ALL |
| 210B | 24 | | PL T | 5-0 | 21-61-21 | D08092P | | | | 21 | | | | TB0164X | C006 | BJ | | ALL |
| 210R | 24 | | PL T | 0-0 | 21-61-21 | D08092P | | | | 22 | | | | TB0164X | D006 | BJ | | ALL |
| 212B | 24 | | PL X | 6-0 | 21-61-51 | D05686P | | | | 42 | | | | TB0164X | A011 | BJ | | 050-099 |
| 212B | 24 | | PL X | 5-0 | 21-61-51 | TB0164X | | | | A011 | BJ | | | D05686P | 42 | | | 150-199 |
| 212B | 24 | | PL X | 5-0 | 21-61-51 | D05686P | | | | 42 | | | | TB0164X | A011 | BJ | | 275-299 |
| 212R | 24 | | PL X | 0-0 | 21-61-51 | D05686P | | | | 43 | | | | TB0164X | B011 | BJ | | 050-099, 275-299 |
| 212R | 24 | | PL X | 0-0 | 21-61-51 | TB0164X | | | | B011 | BJ | | | D05686P | 43 | | | 150-199 |
| 213B | 24 | | PL Y | 3-0 | 21-61-51 | D00958B | | | | A03 | | | | TB0164X | A012 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0080

Page 4

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-----------------|----|-------|------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0082 | 286T0082 | | | SHELF E3-1 LEFT (continued) | | | | | | | | | | | | |
| 213R | 24 | PL | Y | | 0-0 | 21-61-51 | D00958B | A04 | | | | TB0164X | B012 | BJ | | ALL |
| 214B | 24 | PL | Z | | 6-0 | 21-61-51 | D05686P | 36 | | | | TB0164X | C012 | BJ | | 050-099 |
| 214B | 24 | PL | Z | | 5-0 | 21-61-51 | TB0164X | C012 | BJ | | | D05686P | 36 | | | 150-199 |
| 214B | 24 | PL | Z | | 5-0 | 21-61-51 | D05686P | 36 | | | | TB0164X | C012 | BJ | | 275-299 |
| 214R | 24 | PL | Z | | 0-0 | 21-61-51 | D05686P | 38 | | | | TB0164X | D012 | BJ | | 050-099, 275-299 |
| 214R | 24 | PL | Z | | 0-0 | 21-61-51 | TB0164X | D012 | BJ | | | D05686P | 38 | | | 150-199 |
| 215B | 24 | PL | AA | | 3-0 | 21-61-51 | D00958B | B07 | | | | TB0164Y | A014 | BJ | | ALL |
| 215R | 24 | PL | AA | | 0-0 | 21-61-51 | D00958B | B08 | | | | TB0164Y | C014 | BJ | | ALL |
| 216B | 24 | PL | AB | | 3-0 | 21-61-51 | D00958B | A07 | | | | TB0164F | A015 | 2 | | ALL |
| 216R | 24 | PL | AB | | 0-0 | 21-61-51 | D00958B | A08 | | | | TB0164F | C015 | 2 | | ALL |
| 217B | 24 | PL | AC | | 3-0 | 21-61-51 | D00958B | C04 | | | | TB0166X | A004 | BJ | | ALL |
| 217R | 24 | PL | AC | | 0-0 | 21-61-51 | D00958B | C03 | | | | TB0166X | B004 | BJ | | ALL |
| 218B | 24 | PL | AD | | 3-0 | 21-61-51 | D00958B | D04 | | | | TB0166X | C004 | BJ | | ALL |
| 218R | 24 | PL | AD | | 0-0 | 21-61-51 | D00958B | D03 | | | | TB0166X | D004 | BJ | | ALL |
| 219B | 24 | PW | AF | | 4-0 | 21-52-41 | TB0166F | A010 | 2 | | | D01174A | B06 | | | ALL |
| 219R | 24 | PW | AF | | 0-0 | 21-52-41 | TB0166F | C010 | 2 | | | D01174A | B05 | | | ALL |
| 219Z | | | AF | | 0-0 | 21-52-41 | TB0166F | DED | | | | D01174A | DED | | | ALL |
| 220B | 24 | PW | AG | | 4-0 | 21-52-41 | TB0166F | C014 | 2 | | | D01174A | C06 | | | ALL |
| 220R | 24 | PW | AG | | 0-0 | 21-52-41 | TB0166F | A013 | 2 | | | D01174A | C05 | | | ALL |
| 220Z | | | AG | | 0-0 | 21-52-41 | TB0166F | DED | | | | D01174A | DED | | | ALL |
| 221B | 24 | PL | AH | | 5-0 | 21-52-41 | D05686P | 25 | | | | D01174B | B06 | | | ALL |
| 221R | 24 | PL | AH | | 0-0 | 21-52-41 | D05686P | 26 | | | | D01174B | B05 | | | ALL |
| 222B | 24 | PL | AI | | 4-0 | 21-52-41 | D04500P | 17 | | | | D01174B | C06 | | | ALL |
| 222R | 24 | PL | AI | | 0-0 | 21-52-41 | D04500P | 18 | | | | D01174B | C05 | | | ALL |
| 223B | 24 | PL | AJ | | 4-0 | 21-52-41 | D04500P | 44 | | | | D01174B | A01 | | | ALL |
| 223R | 24 | PL | AJ | | 0-0 | 21-52-41 | D04500P | 45 | | | | D01174B | A02 | | | ALL |
| 224B | 24 | PW | AK | | 4-0 | 21-52-41 | TB0166F | C013 | 2 | | | D01174A | A01 | | | ALL |
| 224R | 24 | PW | AK | | 0-0 | 21-52-41 | TB0166F | A014 | 2 | | | D01174A | A02 | | | ALL |
| 224Z | | | AK | | 0-0 | 21-52-41 | TB0166F | DED | | | | D01174A | DED | | | ALL |
| 225B | 24 | PL | AN | | 5-0 | 21-51-11 | D04502P | 21 | | | | D00958B | B01 | | | ALL |
| 225R | 24 | PL | AN | | 0-0 | 21-51-11 | D04502P | 20 | | | | D00958B | B02 | | | ALL |
| 226B | 22 | PB | AO | | 5-0 | 21-51-12 | D00958B | C01 | | | | D05782P | 21 | | | ALL |
| 226R | 22 | PB | AO | | 0-0 | 21-51-12 | D00958B | C02 | | | | D05782P | 20 | | | ALL |
| 227B | 24 | PL | AP | | 3-0 | 21-51-12 | D00958B | D01 | | | | TB0166Y | A011 | BJ | | 050-099, 151-199, 275-299 |
| 227B | 24 | PL | AP | | 3-0 | 21-51-12 | D00958B | D01 | | | | TB0166G | 11 | 2 | | 150 |
| 227R | 24 | PL | AP | | 0-0 | 21-51-12 | D00958B | D02 | | | | TB0166Y | A012 | BJ | | 050-099, 151-199, 275-299 |
| 227R | 24 | PL | AP | | 0-0 | 21-51-12 | D00958B | D02 | | | | TB0166G | 12 | 2 | | 150 |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0082 | 286T0082 | | | SHELF E3-1 LEFT (continued) | | | | | | | | | | | |
| 228B | 24 | PL | AQ | 5-0 | 21-51-12 | D05782P | | 18 | | | | TB0166Y | A011 | BJ | 050-099, 151-199, 275-299 |
| 228B | 24 | PL | AQ | 5-0 | 21-51-12 | D05782P | | 18 | | | | TB0166G | 11 | 2 | 150 |
| 228R | 24 | PL | AQ | 0-0 | 21-51-12 | D05782P | | 19 | | | | TB0166Y | A012 | BJ | 050-099, 151-199, 275-299 |
| 228R | 24 | PL | AQ | 0-0 | 21-51-12 | D05782P | | 19 | | | | TB0166G | 12 | 2 | 150 |
| 229B | 24 | PL | Q | 3-0 | 21-51-12 | D00958B | | C10 | | | | TB0164F | C016 | 2 | ALL |
| 229R | 24 | PL | Q | 0-0 | 21-51-12 | D00958B | | C09 | | | | TB0164F | A016 | 2 | ALL |
| 230B | 24 | PL | AV | 3-0 | 21-51-12 | D00958B | | D10 | | | | TB0164F | C017 | 2 | ALL |
| 230R | 24 | PL | AV | 0-0 | 21-51-12 | D00958B | | D09 | | | | TB0164F | A017 | 2 | ALL |
| 231B | 22 | PB | AX | 4-0 | 21-51-12 | D05782P | | 22 | | | | D05686P | 33 | | ALL |
| 231R | 22 | PB | AX | 0-0 | 21-51-12 | D05782P | | 23 | | | | D05686P | 32 | | ALL |
| 232B | 22 | PB | JG | 6-0 | 21-51-12 | TB0166Y | | C011 | BJ | | | D05686P | 6 | | 050-099 |
| 232B | 22 | PB | JG | 5-0 | 21-51-12 | TB0166Y | | C011 | BJ | | | D05686P | 6 | | 151-199, 275-299 |
| 232R | 22 | PB | JG | 0-0 | 21-51-12 | TB0166Y | | C012 | BJ | | | D05686P | 7 | | 050-099, 151-199, 275-299 |
| 234B | 24 | PL | JI | 5-0 | 21-61-51 | D05686P | | 44 | | | | D00958B | A05 | | ALL |
| 234R | 24 | PL | JI | 0-0 | 21-61-51 | D05686P | | 45 | | | | D00958B | A06 | | ALL |
| 235B | 24 | PL | JJ | 5-0 | 21-61-51 | D05686P | | 46 | | | | D00958B | A01 | | ALL |
| 235R | 24 | PL | JJ | 0-0 | 21-61-51 | D05686P | | 47 | | | | D00958B | A02 | | ALL |
| 236B | 24 | PL | JK | 5-0 | 21-61-51 | TB0164Y | | A014 | BJ | | | D04500P | 38 | | ALL |
| 236R | 24 | PL | JK | 0-0 | 21-61-51 | TB0164Y | | C014 | BJ | | | D04500P | 39 | | ALL |
| 237B | 24 | PL | JL | 5-0 | 21-61-51 | TB0164Y | | A013 | BJ | | | D04502P | 24 | | ALL |
| 237R | 24 | PL | JL | 0-0 | 21-61-51 | TB0164Y | | C013 | BJ | | | D04502P | 25 | | ALL |
| 238B | 22 | PB | JM | 5-0 | 21-51-12 | TB0166Y | | C011 | BJ | | | D04500P | 20 | | 050-099, 151-199, 275-299 |
| 238R | 22 | PB | JM | 0-0 | 21-51-12 | TB0166Y | | C012 | BJ | | | D04500P | 19 | | 050-099, 151-199, 275-299 |
| 239B | 24 | PL | JN | 8-0 | 36-23-11 | D04502P | | 13 | | | | TB0168X | B004 | BJ | 050-099, 162 |
| 239B | 24 | PL | JN | 5-0 | 36-23-11 | D04502P | | 13 | | | | TB0168X | B004 | BJ | 156-157, 166-199, 277-299 |
| 239R | 24 | PL | JN | 0-0 | 36-23-11 | D04502P | | 12 | | | | TB0168X | A004 | BJ | 050-099, 156-162, 166-199, 277-299 |
| 301B | 24 | PM | A | 3-0 | 21-51-12 | TB0166G | | 2 | 2 | | | D00958B | A10 | | 150 |
| 301R | 24 | PM | A | 0-0 | 21-51-12 | TB0166G | | 3 | 2 | | | D00958B | A11 | | 150 |
| 301Y | 24 | PM | A | 0-0 | 21-51-12 | TB0166G | | 1 | 2 | | | D00958B | A09 | | 150 |
| 302B | 22 | PC | J | 5-0 | 21-51-12 | D04500P | | 31 | | | | D00958A | B01 | | ALL |
| 302R | 22 | PC | J | 0-0 | 21-51-12 | D04500P | | 30 | | | | D00958A | B02 | | ALL |
| 302Y | 22 | PC | J | 0-0 | 21-51-12 | D04500P | | 29 | | | | D00958A | B03 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0080

Page 6

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0082 | 286T0082 | | | SHELF E3-1 LEFT (continued) | | | | | | | | | | | |
| 303B | 22 | PC | I | 5-0 | 21-51-12 | D04500P | | 28 | | | D00958A | C01 | | ALL | |
| 303R | 22 | PC | I | 0-0 | 21-51-12 | D04500P | | 27 | | | D00958A | C02 | | ALL | |
| 303Y | 22 | PC | I | 0-0 | 21-51-12 | D04500P | | 26 | | | D00958A | C03 | | ALL | |
| 304B | 22 | PC | H | 5-0 | 21-51-12 | D04500P | | 25 | | | D00958A | A01 | | ALL | |
| 304R | 22 | PC | H | 0-0 | 21-51-12 | D04500P | | 24 | | | D00958A | A02 | | ALL | |
| 304Y | 22 | PC | H | 0-0 | 21-51-12 | D04500P | | 23 | | | D00958A | A03 | | ALL | |
| 305B | 24 | PM | B | 5-0 | 21-51-12 | TB0166G | | 2 | 2 | | D04500P | 10 | | ALL | |
| 305R | 24 | PM | B | 0-0 | 21-51-12 | TB0166D | | | C003 | 2 | D04500P | 11 | | 050-099, 151-199, 275-299 | |
| 305R | 24 | PM | B | 0-0 | 21-51-12 | TB0166G | | 3 | 2 | | D04500P | 11 | | 150 | |
| 305Y | 24 | PM | B | 0-0 | 21-51-12 | TB0166G | | 1 | 2 | | D04500P | 12 | | ALL | |
| 306B | 24 | PM | K | 5-0 | 21-53-11 | D04500P | | 1 | | | D00958A | A11 | | ALL | |
| 306R | 24 | PM | K | 0-0 | 21-53-11 | D04500P | | 2 | | | D00958A | A10 | | ALL | |
| 306Y | 24 | PM | K | 0-0 | 21-53-11 | D04500P | | 3 | | | D00958A | A12 | | ALL | |
| 307B | 24 | PM | L | 5-0 | 21-53-11 | D04500P | | 4 | | | D00958A | C11 | | ALL | |
| 307R | 24 | PM | L | 0-0 | 21-53-11 | D04500P | | 5 | | | D00958A | C10 | | ALL | |
| 307Y | 24 | PM | L | 0-0 | 21-53-11 | D04500P | | 6 | | | D00958A | C12 | | ALL | |
| 308B | 24 | PM | M | 5-0 | 21-53-11 | D04500P | | 7 | | | D00958A | B11 | | ALL | |
| 308R | 24 | PM | M | 0-0 | 21-53-11 | D04500P | | 8 | | | D00958A | B10 | | ALL | |
| 308Y | 24 | PM | M | 0-0 | 21-53-11 | D04500P | | 9 | | | D00958A | B12 | | ALL | |
| 309B | 24 | PM | R | 6-0 | 21-61-11 | D05686P | | 10 | | | TB0164F | A003 | 2 | ALL | |
| 309R | 24 | PM | R | 0-0 | 21-61-11 | D05686P | | 11 | | | TB0164F | C003 | 2 | ALL | |
| 309Y | 24 | PM | R | 0-0 | 21-61-11 | D05686P | | 12 | | | TB0164F | A004 | 2 | ALL | |
| 310B | 24 | PM | U | 6-0 | 21-61-21 | D05686P | | 15 | | | TB0164F | C004 | 2 | ALL | |
| 310R | 24 | PM | U | 0-0 | 21-61-21 | D05686P | | 16 | | | TB0164F | A005 | 2 | ALL | |
| 310Y | 24 | PM | U | 0-0 | 21-61-21 | D05686P | | 17 | | | TB0164F | C005 | 2 | ALL | |
| 311B | 24 | PM | W | 6-0 | 21-61-31 | D05686P | | 20 | | | TB0164F | A009 | 2 | ALL | |
| 311R | 24 | PM | W | 0-0 | 21-61-31 | D05686P | | 21 | | | TB0164F | C009 | 2 | ALL | |
| 311Y | 24 | PM | W | 0-0 | 21-61-31 | D05686P | | 22 | | | TB0164F | A010 | 2 | ALL | |
| 312B | 24 | PX | AE | 5-0 | 36-23-11 | D04502P | | 17 | | | TB0168X | A002 | BJ | 050-099, 156-162, 166-199, 277-299 | |
| 312B | 24 | PX | AE | 5-0 | 36-23-11 | D04502P | | 17 | | | TB0168F | A003 | 2 | 150-155, 163-165, 275-276 | |
| 312R | 24 | PX | AE | 0-0 | 36-23-11 | D04502P | | 18 | | | TB0168X | C002 | BJ | 050-099, 156-162, 166-199, 277-299 | |
| 312R | 24 | PX | AE | 0-0 | 36-23-11 | D04502P | | 18 | | | TB0168F | C003 | 2 | 150-155, 163-165, 275-276 | |
| 312Y | 24 | PX | AE | 0-0 | 36-23-11 | D04502P | | 19 | | | TB0168X | B002 | BJ | 050-099, 156-162, 166-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W0080
Page 7
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|------------------------------------|----|-----|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0082 | 286T0082 | SHELF E3-1 LEFT (continued) | | | | | | | | | | | | | | |
| 312Y | 24 | PX | AE | 0-0 | 36-23-11 | D04502P | 19 | | | | TB0168F | A004 | 2 | | 150-155, 163-165, 275-276 | |
| 312Z | | | AE | 0-0 | 36-23-11 | D04502P | 16 | | | | TB0168X | D002 | BJ | | 050-099, 156-162, 166-199, 277-299 | |
| 312Z | | | AE | 0-0 | 36-23-11 | D04502P | 16 | | | | TB0168F | C004 | 2 | | 150-155, 163-165, 275-276 | |
| 313B | 24 | PM | AY | 4-0 | 21-61-41 | D05686P | 41 | | | | TB0168F | A017 | 2 | | 050-099 | |
| 313B | 24 | PM | AY | 4-0 | 21-61-41 | D05686P | 41 | | | | TB0168X | C016 | BJ | | 150-199, 275-299 | |
| 313R | 24 | PM | AY | 0-0 | 21-61-41 | D05686P | 40 | | | | TB0168F | C016 | 2 | | 050-099 | |
| 313R | 24 | PM | AY | 0-0 | 21-61-41 | D05686P | 40 | | | | TB0168X | B016 | BJ | | 150-199, 275-299 | |
| 313Y | 24 | PM | AY | 0-0 | 21-61-41 | D05686P | 39 | | | | TB0168F | A016 | 2 | | 050-099 | |
| 313Y | 24 | PM | AY | 0-0 | 21-61-41 | D05686P | 39 | | | | TB0168X | A016 | BJ | | 150-199, 275-299 | |
| 401B | 24 | PY | AL | 4-0 | 21-52-41 | D01174A | A05 | | | | TB0166F | A015 | 2 | | ALL | |
| 401G | 24 | PY | AL | 0-0 | 21-52-41 | D01174A | D06 | | | | TB0166F | C015 | 2 | | ALL | |
| 401R | 24 | PY | AL | 0-0 | 21-52-41 | D01174A | A06 | | | | TB0166F | A016 | 2 | | ALL | |
| 401Y | 24 | PY | AL | 0-0 | 21-52-41 | D01174A | D05 | | | | TB0166F | C016 | 2 | | ALL | |
| 401Z | | | AL | 0-0 | 21-52-41 | D01174A | DED | | | | TB0166F | DED | | | ALL | |
| 402B | 24 | PN | AM | 5-0 | 21-52-41 | D01174B | A05 | | | | D05686P | 30 | | | ALL | |
| 402G | 24 | PN | AM | 0-0 | 21-52-41 | D01174B | D06 | | | | D05686P | 27 | | | ALL | |
| 402R | 24 | PN | AM | 0-0 | 21-52-41 | D01174B | A06 | | | | D05686P | 28 | | | ALL | |
| 402Y | 24 | PN | AM | 0-0 | 21-52-41 | D01174B | D05 | | | | D05686P | 29 | | | ALL | |
| 550 | 24 | PK | | 5-0 | 21-51-12 | D05686P | 5 | | | | TB0166D | C003 | 2 | | 050-099, 151-199, 275-299 | |
| 551 | 24 | PK | | 3-0 | 21-51-12 | D00958B | A09 | | | | D00958B | A10 | | | 050-099 | |
| 551 | 24 | PK | | 1-0 | 21-51-12 | D00958B | A09 | | | | D00958B | A10 | | | 151-199, 275-299 | |
| W0084 | 286T0084 | SHELF E3-1 RIGHT | | | | | | | | | | | | | | |
| 001 | 18 | PQ | AY | 5-0 | 21-53-21 | D08052P | 1 | DL | | | D03050C | 2 | | | ALL | |
| 001Z | | | AY | 0-0 | 21-53-21 | D08052P | DED | | | | D03050C | DED | | | ALL | |
| 002 | 24 | PK | | 5-0 | 21-53-21 | D08052P | 2 | | | | D03050B | A15 | | | ALL | |
| 003 | 24 | PK | | 5-0 | 21-53-21 | D08052P | 3 | | | | D03050B | A13 | | | ALL | |
| 004 | 24 | PK | | 5-0 | 21-53-21 | D08052P | 4 | | | | D03050B | B15 | | | ALL | |
| 005 | 24 | PK | | 5-0 | 21-53-21 | D08052P | 5 | | | | D03050B | B13 | | | ALL | |
| 006 | 24 | PK | | 5-0 | 21-53-21 | D08052P | 6 | | | | D03050B | C15 | | | ALL | |
| 007 | 24 | PK | | 5-0 | 21-53-21 | D08052P | 7 | | | | D03050B | C13 | | | ALL | |
| 008 | 18 | PA | | 3-0 | 21-53-21 | D03050C | 4 | | | | GD0001 | A.. | 2 | | ALL | |
| 010 | 22 | PA | | 3-0 | 21-61-11 | D00770A | C15 | | | | GD0001 | D.. | 2 | | ALL | |
| 012 | 24 | PK | | 5-0 | 21-61-51 | D00770B | C03 | | | | D08050P | 47 | | | ALL | |
| 023 | 24 | PK | | 5-0 | 21-61-11 | D00770B | A11 | | | | D04504P | 11 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0080

Page 8

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|--------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0084 | 286T0084 | | | SHELF E3-1 RIGHT (continued) | | | | | | | | | | | | | |
| 024 | 24 | | PK | | 5-0 | 21-61-11 | D00770B | | A12 | | | | D04504P | 12 | | | ALL |
| 025 | 24 | | PK | | 5-0 | 21-61-21 | D00770B | | B11 | | | | D04504P | 18 | | | ALL |
| 026 | 24 | | PK | | 5-0 | 21-61-21 | D00770B | | B12 | | | | D04504P | 19 | | | ALL |
| 027 | 24 | | PK | | 5-0 | 21-61-21 | D04504P | | 35 | | | | TB0166X | D007 | BJ | | ALL |
| 028 | 24 | | PK | | 5-0 | 21-61-21 | D04504P | | 34 | | | | TB0166X | C007 | BJ | | ALL |
| 029 | 24 | | PK | | 5-0 | 21-61-11 | D04504P | | 32 | | | | TB0166X | C006 | BJ | | ALL |
| 030 | 24 | | PK | | 5-0 | 21-61-11 | D04504P | | 33 | | | | TB0166X | D006 | BJ | | ALL |
| 031 | 24 | | PK | | 5-0 | 21-61-31 | D00770B | | C11 | | | | D04504P | 25 | | | ALL |
| 032 | 24 | | PK | | 5-0 | 21-61-31 | D00770B | | C12 | | | | D04504P | 26 | | | ALL |
| 033 | 24 | | PK | | 5-0 | 21-61-31 | TB0166F | | A008 | 2 | | | D04504P | 36 | | | ALL |
| 034 | 24 | | PK | | 5-0 | 21-61-31 | TB0166F | | C008 | 2 | | | D04504P | 55 | | | ALL |
| 035 | 18 | | PQ | BC | 3-0 | 21-61-51 | D00770C | | 2 | | | | TB0164F | C010 | 2 | | ALL |
| 035Z | | | | BC | 0-0 | 21-61-51 | D00770C | | DED | | | | TB0164F | DED | | | ALL |
| 040 | 18 | | PA | | 4-0 | SPARE | D04504P | | 54 | DL | | | GDY0003 | D.. | 2 | | 150-154, 275 |
| 043 | 24 | | PK | | 4-0 | 36-11-62 | D05802P | | 2 | | | | TB0170G | 13 | 2 | | ALL |
| 044 | 24 | | PK | | 4-0 | 36-11-62 | D05802P | | 9 | | | | TB0170G | 13 | 2 | | ALL |
| 049 | 24 | | PK | | 3-0 | 36-23-11 | D02378A | | A07 | | | | TB0168X | A001 | BJ | | ALL |
| 050 | 24 | | PK | | 3-0 | 36-23-11 | D02378A | | A08 | | | | TB0168X | C001 | BJ | | ALL |
| 051 | 24 | | PK | | 3-0 | 36-23-11 | D02378B | | D03 | | | | TB0168X | B001 | BJ | | ALL |
| 052 | 24 | | PK | | 3-0 | 36-23-11 | D02378B | | D06 | | | | TB0168X | D001 | BJ | | ALL |
| 053 | 24 | | PK | | 3-0 | 36-23-11 | D02378A | | A04 | | | | TB0168X | A003 | BJ | | ALL |
| 054 | 24 | | PK | | 3-0 | 36-23-11 | D02378A | | A10 | | | | TB0168X | C003 | BJ | | ALL |
| 055 | 24 | | PK | | 3-0 | 36-23-11 | D02378A | | D15 | | | | TB0168G | 11 | 2 | | ALL |
| 056 | 24 | | PK | | 3-0 | 36-23-11 | D02378A | | D05 | | | | TB0168G | 13 | 2 | | ALL |
| 057 | 24 | | PK | | 3-0 | 36-23-11 | D02378A | | A06 | | | | TB0166F | C009 | 2 | | ALL |
| 058 | 24 | | PK | | 3-0 | 36-23-11 | D02378A | | D01 | | | | TB0168F | A008 | 2 | | ALL |
| 059 | 24 | | PK | | 3-0 | 36-23-11 | D02378B | | A06 | | | | TB0168G | 10 | 2 | | ALL |
| 060 | 24 | | PK | | 3-0 | 36-23-11 | D02378B | | D02 | | | | TB0168X | B003 | BJ | | ALL |
| 061 | 24 | | PK | | 3-0 | 36-23-11 | D02378B | | D04 | | | | TB0168X | D003 | BJ | | ALL |
| 062 | 24 | | PK | | 3-0 | 36-23-11 | D02378B | | D13 | | | | TB0168F | A007 | 2 | | ALL |
| 063 | 24 | | PK | | 3-0 | 36-23-11 | D02378B | | D08 | | | | TB0168F | C007 | 2 | | ALL |
| 064 | 22 | | PA | | 3-0 | 36-23-11 | D02378B | | A04 | | | | TB0166X | D005 | BJ | | ALL |
| 065 | 22 | | PA | | 3-0 | 36-23-11 | D02378B | | D12 | | | | TB0166X | C005 | BJ | | ALL |
| 066 | 24 | | PK | | 3-0 | 36-23-11 | D02378B | | D05 | | | | TB0168F | A009 | 2 | | ALL |
| 067 | 24 | | PK | | 3-0 | 36-23-11 | D02378B | | A10 | | | | TB0168G | 15 | 2 | | ALL |
| 068 | 24 | | PK | | 3-0 | 36-23-11 | D02378B | | A07 | | | | TB0166F | A009 | 2 | | ALL |
| 069 | 18 | | PQ | AZ | 3-0 | 36-23-11 | D02378C | | 4 | | | | TB0168F | C009 | 2 | | ALL |
| 069Z | | | | AZ | 0-0 | 36-23-11 | D02378C | | DED | | | | TB0168F | DED | | | ALL |
| 070 | 20 | | UA | | 3-0 | 36-23-11 | D02378A | | | | FA | | GDY0003 | S.. | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0080
Page 9
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|--|---|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0084 | 286T0084 | | | SHELF E3-1 RIGHT (continued) | | | | | | | | | | | | | | |
| 071 | 24 | | PK | 1-0 | 21-51-22 | D03050B | | B05 | | | | | D03050B | | B06 | | | ALL |
| 072 | 18 | | PA | 3-0 | 36-23-11 | D02378C | | | 2 | | | | GD0003 | | A.. | 2 | | ALL |
| 073 | 22 | | PA | 3-0 | 36-23-11 | D02378B | | A02 | | | | | GD0003 | | D.. | 2 | | ALL |
| 074 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | A12 | | | | | D05802P | | 15 | | | ALL |
| 075 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | A11 | | | | | D05802P | | 16 | | | ALL |
| 076 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | D10 | | | | | D05802P | | 17 | | | ALL |
| 077 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | D11 | | | | | D05802P | | 19 | | | ALL |
| 078 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | A03 | | | | | D04504P | | 46 | | | ALL |
| 079 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | A09 | | | | | D04504P | | 49 | | | ALL |
| 080 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | D08 | | | | | D04504P | | 50 | | | ALL |
| 081 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | D07 | | | | | D04504P | | 51 | | | ALL |
| 082 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | D13 | | | | | D05802P | | 5 | | | ALL |
| 083 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | D12 | | | | | D05802P | | 6 | | | ALL |
| 084 | 24 | | PK | 3-0 | 36-23-21 | D02378A | | D06 | | | | | TB0170G | | 13 | 2 | | ALL |
| 085 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | D09 | | | | | D05802P | | 10 | | | ALL |
| 086 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | A05 | | | | | D05802P | | 11 | | | ALL |
| 087 | 24 | | PK | 4-0 | 36-23-21 | D02378A | | A01 | | | | | D05802P | | 24 | | | ALL |
| 088 | 18 | | PA | 3-0 | 36-23-21 | D02378C | | | 3 | | | | GD0003 | | S.. | 2 | | ALL |
| 089 | 24 | | PK | 4-0 | 36-23-21 | D02378B | | D10 | | | | | D04504P | | 47 | | | ALL |
| 090 | 24 | | PK | 4-0 | 36-23-21 | D02378B | | D11 | | | | | D04504P | | 48 | | | 050-099, 150-155, 157-165, 167-199, 275-299 |
| 090 | 24 | | PK | 5-0 | 36-23-21 | D02378B | | D11 | | | | | D04504P | | 48 | | | 156, 166 |
| 091 | 22 | | PA | 4-0 | 36-23-21 | D02378B | | A08 | | | | | D05802P | | 42 | | | ALL |
| 092 | 22 | | PA | 4-0 | 36-23-21 | D02378B | | D09 | | | | | D05802P | | 43 | | | ALL |
| 093 | 24 | | PK | 4-0 | 36-23-21 | D02378B | | A11 | | | | | D05802P | | 14 | | | ALL |
| 094 | 24 | | PK | 4-0 | 36-23-21 | D02378B | | A05 | | | | | D05802P | | 25 | | | ALL |
| 095 | 24 | | PK | 4-0 | 36-23-21 | D02378B | | A01 | | | | | D08050P | | 34 | | | ALL |
| 096 | 24 | | PK | 4-0 | 36-23-21 | D02378B | | A03 | | | | | D08050P | | 35 | | | ALL |
| 097 | 20 | | PA | 4-0 | 36-23-21 | D05802P | | | 18 | | | | GD0003 | | D.. | 2 | | ALL |
| 098 | 20 | | UA | 3-0 | 36-23-21 | D02378A | | | | | FB | | GD0003 | | S.. | 2 | | ALL |
| 100 | 20 | | PA | 5-0 | 36-11-52 | D04504P | | | 7 | | | | GD0001 | | D.. | 2 | | ALL |
| 101 | 20 | | PA | 4-0 | 36-11-52 | D04504P | | | 8 | | | | GD0003 | | D.. | 2 | | ALL |
| 102 | 20 | | PQ | 3-0 | 21-61-51 | D00770C | | | 4 | | | | GD0001 | | A.. | 2 | | ALL |
| 102Z | | | | 0-0 | 21-61-51 | D00770C | | | | DED | | | GD0001 | | DED | | | ALL |
| 104 | 18 | | PA | 3-0 | 21-53-21 | D03050C | | | 3 | | | | GD0001 | | S.. | 2 | | ALL |
| 105 | 24 | | PK | 5-0 | 21-53-21 | D03050B | | D07 | | | | | D08052P | | 8 | | | ALL |
| 106 | 24 | | PK | 5-0 | 21-51-21 | D03050B | | C07 | | | | | D08052P | | 15 | | | ALL |
| 108 | 22 | | PA | 5-0 | 21-51-21 | D03050B | | C05 | | | | | D08052P | | 16 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0080

Page 10

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0084 | 286T0084 | | | SHELF E3-1 RIGHT (continued) | | | | | | | | | | | |
| 110 | 22 | PA | | | 5-0 | 21-61-11 | D00770B | A09 | | | D05802P | 30 | | | ALL |
| 111 | 22 | PA | | | 2-0 | 21-61-11 | D00770B | C04 | | | GDY0001 | D.. | 2 | | ALL |
| 112 | 24 | PK | | | 5-0 | 21-61-21 | D00770B | B09 | | | D05802P | 29 | | | ALL |
| 113 | 24 | PK | | | 5-0 | 21-61-31 | D00770B | C09 | | | D05802P | 28 | | | ALL |
| 117 | 24 | PK | | | 4-0 | 21-51-21 | D08050P | 48 | | | D03050B | B09 | | | ALL |
| 118 | 22 | PA | | | 4-0 | 21-51-22 | D03050A | C15 | | | GDY0001 | D.. | 2 | | ALL |
| 119 | 24 | PK | | | 5-0 | 21-61-41 | D05802P | 32 | | | TB0164F | C008 | 2 | | ALL |
| 120 | 24 | PK | | | 5-0 | 21-61-41 | D05802P | 33 | | | TB0164F | A008 | 2 | | ALL |
| 121 | 24 | PK | | | 5-0 | 21-61-41 | D05802P | 36 | | | D00770B | D12 | | | ALL |
| 122 | 24 | PK | | | 5-0 | 21-61-41 | D05802P | 37 | | | D00770B | D11 | | | ALL |
| 123 | 24 | PK | | | 5-0 | 21-61-41 | D05802P | 38 | | | D00770B | D09 | | | ALL |
| 125 | 24 | PK | | | 2-0 | 21-51-21 | D03050B | B03 | | | D03050B | B04 | | | 150-199, 275-299 |
| 128 | 24 | PK | | | 4-0 | 21-51-11 | D05802P | 12 | | | TB0168X | A017 | BJ | | 150-199, 275-299 |
| 129 | 24 | PK | | | 4-0 | 21-51-11 | D05802P | 13 | | | TB0168X | B017 | BJ | | 150-199, 275-299 |
| 130 | 24 | PK | | | 3-0 | 21-51-21 | D03050B | B11 | | | TB0170F | C007 | 2 | | 150-199, 275-299 |
| 131 | 24 | PK | | | 3-0 | 21-51-21 | D03050B | B12 | | | TB0170F | A008 | 2 | | 150-199, 275-299 |
| 139 | 24 | PK | | | 5-0 | 21-61-11 | D04504P | 1 | | | TB0166X | A006 | BJ | | ALL |
| 140 | 24 | PK | | | 5-0 | 21-61-11 | D04504P | 4 | | | TB0166X | B006 | BJ | | ALL |
| 141 | 24 | PK | | | 5-0 | 21-61-21 | D04504P | 9 | | | TB0166X | A007 | BJ | | ALL |
| 142 | 24 | PK | | | 5-0 | 21-61-21 | D04504P | 40 | | | TB0166X | B007 | BJ | | ALL |
| 143 | 24 | PK | | | 5-0 | 21-61-31 | D04504P | 42 | | | TB0166X | A005 | BJ | | ALL |
| 144 | 24 | PK | | | 5-0 | 21-61-31 | D04504P | 37 | | | TB0166X | B005 | BJ | | ALL |
| 145 | 24 | PK | | | 5-0 | 21-61-41 | D05802P | 26 | | | TB0164X | A007 | BJ | | ALL |
| 146 | 24 | PK | | | 5-0 | 21-61-41 | D05802P | 27 | | | TB0164X | B007 | BJ | | ALL |
| 150 | 24 | PK | | | 3-0 | 36-23-11 | D02378A | B01 | | | TB0168X | A006 | BJ | | ALL |
| 152 | 24 | PK | | | 4-0 | 36-23-21 | D02378A | B05 | | | D08050P | 42 | | | ALL |
| 155 | 24 | PK | | | 3-0 | 36-23-11 | D02378B | B03 | | | TB0168X | C004 | BJ | | ALL |
| 156 | 24 | PK | | | 3-0 | 36-23-11 | D02378B | B02 | | | TB0168X | D004 | BJ | | ALL |
| 157 | 24 | PK | | | 3-0 | 36-23-11 | D02378A | B03 | | | TB0168X | A005 | BJ | | ALL |
| 159 | 22 | PA | | | 3-0 | 36-23-11 | D02378A | B04 | | | TB0168X | B005 | BJ | | ALL |
| 160 | 22 | PA | | | 3-0 | 36-23-11 | D02378A | B09 | | | TB0168X | C005 | BJ | | ALL |
| 161 | 22 | PA | | | 3-0 | 36-23-11 | D02378A | B10 | | | TB0168X | D005 | BJ | | ALL |
| 163 | 22 | PA | | | 3-0 | 36-23-11 | D02378A | B02 | | | GDY0003 | D.. | 2 | | ALL |
| 167 | 22 | PA | | | 4-0 | 36-23-21 | D05802P | 46 | | | D02378A | B13 | | | ALL |
| 168 | 22 | PA | | | 4-0 | 36-23-21 | D05802P | 47 | | | D02378A | B14 | | | ALL |
| 169 | 24 | PK | | | 4-0 | 36-23-21 | D05802P | 45 | | | D02378A | B08 | | | ALL |
| 170 | 24 | PK | | | 4-0 | 36-23-21 | D08050P | 52 | | | D02378A | B07 | | | ALL |
| 171 | 24 | PK | | | 4-0 | 36-23-21 | D08050P | 53 | | | D02378B | B05 | | | ALL |
| 172 | 24 | PK | | | 4-0 | 36-23-21 | D08050P | 54 | | | D02378B | B04 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0080

Page 11

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0084 | 286T0084 | | | SHELF E3-1 RIGHT (continued) | | | | | | | | | | | | |
| 201B | 22 | PB | A | 4-0 | 21-51-22 | D08050P | | | 19 | D03050A | D04 | | | ALL | | |
| 201R | 22 | PB | A | 0-0 | 21-51-22 | D08050P | | | 20 | D03050A | D05 | | | ALL | | |
| 202B | 22 | PB | B | 4-0 | 21-51-22 | D08050P | | | 21 | D03050A | A04 | | | ALL | | |
| 202R | 22 | PB | B | 0-0 | 21-51-22 | D08050P | | | 22 | D03050A | A05 | | | ALL | | |
| 203B | 22 | PB | C | 5-0 | 21-51-22 | D05738P | | | 1 | D03050A | C05 | | | ALL | | |
| 203R | 22 | PB | C | 0-0 | 21-51-22 | D05738P | | | 2 | D03050A | C04 | | | ALL | | |
| 204B | 22 | PB | D | 4-0 | 21-51-22 | D08050P | | | 25 | D03050A | B05 | | | ALL | | |
| 204R | 22 | PB | D | 0-0 | 21-51-22 | D08050P | | | 26 | D03050A | B04 | | | ALL | | |
| 205B | 24 | PL | E | 4-0 | 21-51-22 | D08050P | | | 27 | D03050B | D05 | | | ALL | | |
| 205R | 24 | PL | E | 0-0 | 21-51-22 | D08050P | | | 28 | D03050B | D06 | | | ALL | | |
| 206B | 24 | PL | M | 3-0 | 21-61-11 | D00770A | | | A06 | TB0164F | C001 | 2 | | ALL | | |
| 206R | 24 | PL | M | 0-0 | 21-61-11 | D00770A | | | A07 | TB0164F | A001 | 2 | | ALL | | |
| 207B | 24 | PL | N | 3-0 | 21-61-11 | D00770A | | | A04 | TB0164F | C002 | 2 | | ALL | | |
| 207R | 24 | PL | N | 0-0 | 21-61-11 | D00770A | | | A05 | TB0164F | A002 | 2 | | ALL | | |
| 208B | 24 | PL | O | 5-0 | 21-61-11 | D00770B | | | A13 | D04504P | 13 | | | ALL | | |
| 208R | 24 | PL | O | 0-0 | 21-61-11 | D00770B | | | A15 | D04504P | 14 | | | ALL | | |
| 209B | 24 | PL | T | 3-0 | 21-61-21 | D00770A | | | B04 | TB0164X | A006 | BJ | | ALL | | |
| 209R | 24 | PL | T | 0-0 | 21-61-21 | D00770A | | | B05 | TB0164X | B006 | BJ | | ALL | | |
| 210B | 24 | PL | U | 3-0 | 21-61-21 | D00770A | | | B06 | TB0164X | C006 | BJ | | ALL | | |
| 210R | 24 | PL | U | 0-0 | 21-61-21 | D00770A | | | B07 | TB0164X | D006 | BJ | | ALL | | |
| 211B | 24 | PL | V | 5-0 | 21-61-21 | D00770B | | | B13 | D04504P | 20 | | | ALL | | |
| 211R | 24 | PL | V | 0-0 | 21-61-21 | D00770B | | | B15 | D04504P | 21 | | | ALL | | |
| 212B | 24 | PL | W | 5-0 | 21-61-31 | D00770A | | | C04 | D05738P | 3 | | | ALL | | |
| 212R | 24 | PL | W | 0-0 | 21-61-31 | D00770A | | | C05 | D05738P | 4 | | | ALL | | |
| 213B | 24 | PL | X | 5-0 | 21-61-31 | D00770A | | | C06 | D05738P | 6 | | | ALL | | |
| 213R | 24 | PL | X | 0-0 | 21-61-31 | D00770A | | | C07 | D05738P | 7 | | | ALL | | |
| 214B | 24 | PL | Y | 5-0 | 21-61-31 | D00770B | | | C13 | D04504P | 27 | | | ALL | | |
| 214R | 24 | PL | Y | 0-0 | 21-61-31 | D00770B | | | C15 | D04504P | 28 | | | ALL | | |
| 215B | 24 | PL | AB | 3-0 | 21-61-51 | D00770B | | | C07 | TB0164Y | A014 | BJ | | ALL | | |
| 215R | 24 | PL | AB | 0-0 | 21-61-51 | D00770B | | | C08 | TB0164Y | C014 | BJ | | ALL | | |
| 216B | 24 | PL | AC | 3-0 | 21-61-51 | D00770B | | | A07 | TB0164F | A015 | 2 | | ALL | | |
| 216R | 24 | PL | AC | 0-0 | 21-61-51 | D00770B | | | A08 | TB0164F | C015 | 2 | | ALL | | |
| 217B | 24 | PL | AD | 3-0 | 21-61-51 | D03050B | | | D04 | TB0166X | A004 | BJ | | ALL | | |
| 217R | 24 | PL | AD | 0-0 | 21-61-51 | D03050B | | | D03 | TB0166X | B004 | BJ | | ALL | | |
| 218B | 24 | PL | AE | 3-0 | 21-61-51 | D03050B | | | C04 | TB0166X | C004 | BJ | | ALL | | |
| 218R | 24 | PL | AE | 0-0 | 21-61-51 | D03050B | | | C03 | TB0166X | D004 | BJ | | ALL | | |
| 219B | 24 | PL | AF | 3-0 | 21-61-51 | D00770B | | | A01 | TB0164X | A011 | BJ | | ALL | | |
| 219R | 24 | PL | AF | 0-0 | 21-61-51 | D00770B | | | A02 | TB0164X | B011 | BJ | | ALL | | |
| 220B | 24 | PL | AG | 3-0 | 21-61-51 | D00770B | | | A03 | TB0164X | A012 | BJ | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0080

Page 12

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0084 | 286T0084 | | | SHELF E3-1 RIGHT (continued) | | | | | | | | | | | |
| 220R | 24 | PL | AG | | 0-0 | 21-61-51 | D00770B | A04 | | | TB0164X | B012 | BJ | | ALL |
| 221B | 24 | PL | AH | | 5-0 | 21-61-51 | D00770B | D03 | | | D08050P | 32 | | | ALL |
| 221R | 24 | PL | AH | | 0-0 | 21-61-51 | D00770B | D04 | | | D08050P | 33 | | | ALL |
| 222B | 22 | PB | AI | | 5-0 | 21-61-51 | D00770B | C01 | | | D04504P | 38 | | | ALL |
| 222R | 22 | PB | AI | | 0-0 | 21-61-51 | D00770B | C02 | | | D04504P | 39 | | | ALL |
| 223B | 24 | PL | AJ | | 3-0 | 21-61-51 | D00770B | D07 | | | TB0164Y | A013 | BJ | | ALL |
| 223R | 24 | PL | AJ | | 0-0 | 21-61-51 | D00770B | D08 | | | TB0164Y | C013 | BJ | | ALL |
| 224B | 24 | PL | AK | | 3-0 | 21-61-51 | D00770B | B07 | | | D03050B | A07 | | | ALL |
| 224R | 24 | PL | AK | | 0-0 | 21-61-51 | D00770B | B08 | | | D03050B | A08 | | | ALL |
| 225B | 24 | PL | AL | | 3-0 | 21-61-51 | D00770B | B01 | | | D03050B | A01 | | | ALL |
| 225R | 24 | PL | AL | | 0-0 | 21-61-51 | D00770B | B02 | | | D03050B | A02 | | | ALL |
| 226B | 24 | PL | AM | | 3-0 | 21-61-51 | D00770B | B03 | | | D03050B | A03 | | | ALL |
| 226R | 24 | PL | AM | | 0-0 | 21-61-51 | D00770B | B04 | | | D03050B | A04 | | | ALL |
| 227B | 24 | PL | AN | | 3-0 | 21-61-51 | D00770B | B05 | | | D03050B | A05 | | | ALL |
| 227R | 24 | PL | AN | | 0-0 | 21-61-51 | D00770B | B06 | | | D03050B | A06 | | | ALL |
| 228B | 24 | PL | AQ | | 3-0 | 21-61-51 | D00770B | A05 | | | TB0164X | C012 | BJ | | ALL |
| 228R | 24 | PL | AQ | | 0-0 | 21-61-51 | D00770B | A06 | | | TB0164X | D012 | BJ | | ALL |
| 229B | 24 | PL | AR | | 5-0 | 21-52-41 | D08050P | 23 | | | TB0166F | A010 | 2 | | ALL |
| 229R | 24 | PL | AR | | 0-0 | 21-52-41 | D08050P | 24 | | | TB0166F | C010 | 2 | | ALL |
| 230B | 24 | PL | AS | | 5-0 | 21-52-41 | D08050P | 41 | | | TB0166F | C014 | 2 | | ALL |
| 230R | 24 | PL | AS | | 0-0 | 21-52-41 | D08050P | 40 | | | TB0166F | A013 | 2 | | ALL |
| 231B | 24 | PL | AT | | 4-0 | 21-52-41 | D08050P | 45 | | | TB0166F | C013 | 2 | | ALL |
| 231R | 24 | PL | AT | | 0-0 | 21-52-41 | D08050P | 46 | | | TB0166F | A014 | 2 | | ALL |
| 232B | 24 | PL | AV | | 5-0 | 21-51-21 | D08052P | 14 | | | D03050B | B01 | | | ALL |
| 232R | 24 | PL | AV | | 0-0 | 21-51-21 | D08052P | 13 | | | D03050B | B02 | | | ALL |
| 233B | 24 | PL | AW | | 3-0 | 21-51-22 | D03050B | D01 | | | TB0166Y | A011 | BJ | | 050-099, 151-199, 275-299 |
| 233B | 24 | PL | AW | | 3-0 | 21-51-22 | D03050B | D01 | | | TB0166G | 11 | 2 | | 150 |
| 233R | 24 | PL | AW | | 0-0 | 21-51-22 | D03050B | D02 | | | TB0166Y | A012 | BJ | | 050-099, 151-199, 275-299 |
| 233R | 24 | PL | AW | | 0-0 | 21-51-22 | D03050B | D02 | | | TB0166G | 12 | 2 | | 150 |
| 234B | 22 | PB | AX | | 5-0 | 21-51-22 | D03050B | C01 | | | D08052P | 10 | | | ALL |
| 234R | 22 | PB | AX | | 0-0 | 21-51-22 | D03050B | C02 | | | D08052P | 9 | | | ALL |
| 235B | 24 | PL | BA | | 3-0 | 21-51-22 | D03050B | D10 | | | TB0164F | C016 | 2 | | ALL |
| 235R | 24 | PL | BA | | 0-0 | 21-51-22 | D03050B | D09 | | | TB0164F | A016 | 2 | | ALL |
| 236B | 24 | PL | BB | | 3-0 | 21-51-22 | D03050B | C10 | | | TB0164F | C017 | 2 | | ALL |
| 236R | 24 | PL | BB | | 0-0 | 21-51-22 | D03050B | C09 | | | TB0164F | A017 | 2 | | ALL |
| 237B | 22 | PB | BE | | 3-0 | 21-51-22 | D08052P | 11 | | | D08050P | 44 | | | ALL |
| 237R | 22 | PB | BE | | 0-0 | 21-51-22 | D08052P | 12 | | | D08050P | 43 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0080

Page 13

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0084 | 286T0084 | | | SHELF E3-1 RIGHT (continued) | | | | | | | | | | | | |
| 238B | 24 | PL | BF | | 5-0 | 21-61-41 | D05802P | | 35 | | | | D00770B | D13 | | ALL |
| 238R | 24 | PL | BF | | 0-0 | 21-61-41 | D05802P | | 34 | | | | D00770B | D15 | | ALL |
| 239B | 24 | PL | BG | | 5-0 | 21-61-41 | D05738P | | 9 | | | | D00770A | D06 | | ALL |
| 239R | 24 | PL | BG | | 0-0 | 21-61-41 | D05738P | | 8 | | | | D00770A | D07 | | ALL |
| 240B | 24 | PL | BH | | 5-0 | 21-61-41 | D05738P | | 11 | | | | D00770A | D04 | | ALL |
| 240R | 24 | PL | BH | | 0-0 | 21-61-41 | D05738P | | 10 | | | | D00770A | D05 | | ALL |
| 241B | 24 | PL | JP | | 3-0 | 21-61-51 | TB0164Y | A013 | | BJ | | | D03050B | B07 | | ALL |
| 241R | 24 | PL | JP | | 0-0 | 21-61-51 | TB0164Y | C013 | | BJ | | | D03050B | B08 | | ALL |
| 269B | 24 | PL | KS | | 3-0 | 36-23-11 | D02378B | | B07 | | | | TB0168X | B004 | BJ | ALL |
| 269R | 24 | PL | KS | | 0-0 | 36-23-11 | D02378B | | B06 | | | | TB0168X | A004 | BJ | ALL |
| 271B | 24 | PL | KU | | 4-0 | 36-23-21 | D05802P | | 52 | | | | D02378B | B09 | | ALL |
| 271R | 24 | PL | KU | | 0-0 | 36-23-21 | D05802P | | 51 | | | | D02378B | B08 | | ALL |
| 272 | 20 | UA | | | 3-0 | 36-23-21 | D02378B | | | | FC | | GDX0003 | S.. | 2 | 156-162, 166-199, 277-299 |
| 272B | 24 | PW | BO | | 4-0 | 36-23-21 | D02378B | | C15 | | | | D05802P | 54 | | 156-162, 166-199, 277-299 |
| 272R | 24 | PW | BO | | 0-0 | 36-23-21 | D02378B | | D15 | | | | D05802P | 53 | | 156-162, 166-199, 277-299 |
| 272Z | | | BO | | 0-0 | 36-23-21 | D02378B | | | | FC | | D05802P | 55 | | 156-162, 166-199, 277-299 |
| 301B | 24 | PM | J | | 4-0 | 21-53-21 | D08050P | | 1 | | | | D03050A | A11 | | ALL |
| 301R | 24 | PM | J | | 0-0 | 21-53-21 | D08050P | | 2 | | | | D03050A | A10 | | ALL |
| 301Y | 24 | PM | J | | 0-0 | 21-53-21 | D08050P | | 3 | | | | D03050A | A12 | | ALL |
| 302B | 24 | PM | K | | 4-0 | 21-53-21 | D08050P | | 4 | | | | D03050A | C11 | | ALL |
| 302R | 24 | PM | K | | 0-0 | 21-53-21 | D08050P | | 5 | | | | D03050A | C10 | | ALL |
| 302Y | 24 | PM | K | | 0-0 | 21-53-21 | D08050P | | 6 | | | | D03050A | C12 | | ALL |
| 303B | 24 | PM | L | | 4-0 | 21-53-21 | D08050P | | 7 | | | | D03050A | B11 | | ALL |
| 303R | 24 | PM | L | | 0-0 | 21-53-21 | D08050P | | 8 | | | | D03050A | B10 | | ALL |
| 303Y | 24 | PM | L | | 0-0 | 21-53-21 | D08050P | | 9 | | | | D03050A | B12 | | ALL |
| 304B | 22 | PC | I | | 4-0 | 21-51-22 | D08050P | | 16 | | | | D03050A | A01 | | ALL |
| 304R | 22 | PC | I | | 0-0 | 21-51-22 | D08050P | | 17 | | | | D03050A | A02 | | ALL |
| 304Y | 22 | PC | I | | 0-0 | 21-51-22 | D08050P | | 18 | | | | D03050A | A03 | | ALL |
| 305B | 24 | PM | F | | 3-0 | 21-51-22 | D03050B | A10 | | | | | TB0166G | 2 | 2 | ALL |
| 305R | 24 | PM | F | | 0-0 | 21-51-22 | D03050B | A11 | | | | | TB0166D | A003 | 2 | 050-099, 151-199, 275-299 |
| 305R | 24 | PM | F | | 0-0 | 21-51-22 | D03050B | A11 | | | | | TB0166G | 3 | 2 | 150 |
| 305Y | 24 | PM | F | | 0-0 | 21-51-22 | D03050B | A09 | | | | | TB0166G | 1 | 2 | ALL |
| 306B | 22 | PC | G | | 4-0 | 21-51-22 | D08050P | | 10 | | | | D03050A | B01 | | ALL |
| 306R | 22 | PC | G | | 0-0 | 21-51-22 | D08050P | | 11 | | | | D03050A | B02 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0080

Page 14

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0084 | 286T0084 | | | SHELF E3-1 RIGHT (continued) | | | | | | | | | | | | |
| 306Y | 22 | PC | G | | 0-0 | 21-51-22 | D08050P | | 12 | | | D03050A | B03 | | | ALL |
| 307B | 22 | PC | H | | 4-0 | 21-51-22 | D08050P | | 13 | | | D03050A | C01 | | | ALL |
| 307R | 22 | PC | H | | 0-0 | 21-51-22 | D08050P | | 14 | | | D03050A | C02 | | | ALL |
| 307Y | 22 | PC | H | | 0-0 | 21-51-22 | D08050P | | 15 | | | D03050A | C03 | | | ALL |
| 308B | 24 | PM | P | | 5-0 | 21-61-11 | D00770A | A01 | | | | D04504P | 15 | | | ALL |
| 308R | 24 | PM | P | | 0-0 | 21-61-11 | D00770A | A02 | | | | D04504P | 16 | | | ALL |
| 308Y | 24 | PM | P | | 0-0 | 21-61-11 | D00770A | A03 | | | | D04504P | 17 | | | ALL |
| 309B | 24 | PM | Q | | 3-0 | 21-61-11 | D00770A | A10 | | | | TB0164F | A003 | 2 | | ALL |
| 309R | 24 | PM | Q | | 0-0 | 21-61-11 | D00770A | A11 | | | | TB0164F | C003 | 2 | | ALL |
| 309Y | 24 | PM | Q | | 0-0 | 21-61-11 | D00770A | A12 | | | | TB0164F | A004 | 2 | | ALL |
| 310B | 24 | PM | R | | 3-0 | 21-61-21 | D00770A | B10 | | | | TB0164F | C004 | 2 | | ALL |
| 310R | 24 | PM | R | | 0-0 | 21-61-21 | D00770A | B11 | | | | TB0164F | A005 | 2 | | ALL |
| 310Y | 24 | PM | R | | 0-0 | 21-61-21 | D00770A | B12 | | | | TB0164F | C005 | 2 | | ALL |
| 311B | 24 | PM | S | | 5-0 | 21-61-21 | D00770A | B01 | | | | D04504P | 22 | | | ALL |
| 311R | 24 | PM | S | | 0-0 | 21-61-21 | D00770A | B02 | | | | D04504P | 23 | | | ALL |
| 311Y | 24 | PM | S | | 0-0 | 21-61-21 | D00770A | B03 | | | | D04504P | 24 | | | ALL |
| 312B | 24 | PM | Z | | 3-0 | 21-61-31 | D00770A | C10 | | | | TB0164F | A009 | 2 | | ALL |
| 312R | 24 | PM | Z | | 0-0 | 21-61-31 | D00770A | C11 | | | | TB0164F | C009 | 2 | | ALL |
| 312Y | 24 | PM | Z | | 0-0 | 21-61-31 | D00770A | C12 | | | | TB0164F | A010 | 2 | | ALL |
| 313B | 24 | PM | AA | | 5-0 | 21-61-31 | D00770A | C01 | | | | D04504P | 29 | | | ALL |
| 313R | 24 | PM | AA | | 0-0 | 21-61-31 | D00770A | C02 | | | | D04504P | 30 | | | ALL |
| 313Y | 24 | PM | AA | | 0-0 | 21-61-31 | D00770A | C03 | | | | D04504P | 31 | | | ALL |
| 314B | 24 | PX | AO | | 3-0 | 36-23-11 | D02378A | A14 | | | | TB0168X | A002 | BJ | | ALL |
| 314R | 24 | PX | AO | | 0-0 | 36-23-11 | D02378A | A15 | | | | TB0168X | C002 | BJ | | ALL |
| 314Y | 24 | PX | AO | | 0-0 | 36-23-11 | D02378A | A13 | | | | TB0168X | B002 | BJ | | ALL |
| 314Z | | | AO | | 0-0 | 36-23-11 | D02378A | | | FA | | TB0168X | D002 | BJ | | ALL |
| 315B | 24 | PX | AP | | 4-0 | 36-23-21 | D02378A | A02 | | | | D05802P | 21 | | | ALL |
| 315R | 24 | PX | AP | | 0-0 | 36-23-21 | D02378A | D03 | | | | D05802P | 22 | | | ALL |
| 315Y | 24 | PX | AP | | 0-0 | 36-23-21 | D02378A | D02 | | | | D05802P | 23 | | | ALL |
| 315Z | | | AP | | 0-0 | 36-23-21 | D02378A | | | FB | | D05802P | 20 | | | ALL |
| 316B | 24 | PM | BI | | 5-0 | 21-61-41 | D05802P | 39 | | | | D00770A | D01 | | | ALL |
| 316R | 24 | PM | BI | | 0-0 | 21-61-41 | D05802P | 40 | | | | D00770A | D02 | | | ALL |
| 316Y | 24 | PM | BI | | 0-0 | 21-61-41 | D05802P | 41 | | | | D00770A | D03 | | | ALL |
| 317B | 24 | PM | BJ | | 4-0 | 21-61-41 | TB0168F | A017 | 2 | | | D00770A | D10 | | | 050-099 |
| 317B | 24 | PM | BJ | | 4-0 | 21-61-41 | TB0168X | C016 | BJ | | | D00770A | D10 | | | 150-199, 275-299 |
| 317R | 24 | PM | BJ | | 0-0 | 21-61-41 | TB0168F | C016 | 2 | | | D00770A | D11 | | | 050-099 |
| 317R | 24 | PM | BJ | | 0-0 | 21-61-41 | TB0168X | B016 | BJ | | | D00770A | D11 | | | 150-199, 275-299 |
| 317Y | 24 | PM | BJ | | 0-0 | 21-61-41 | TB0168F | A016 | 2 | | | D00770A | D12 | | | 050-099 |
| 317Y | 24 | PM | BJ | | 0-0 | 21-61-41 | TB0168X | A016 | BJ | | | D00770A | D12 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0080

Page 15

Jan 21/2005



| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|-------------|-------|-------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0084 | 286T0084 | | | | | SHELF E3-1 RIGHT (continued) | | | | | | | | | |
| 401B | 24 | PN | AU | | 5-0 | 21-52-41 | D08050P | | 39 | | TB0166F | A015 | 2 | | ALL |
| 401G | 24 | PN | AU | | 0-0 | 21-52-41 | D08050P | | 36 | | TB0166F | C015 | 2 | | ALL |
| 401R | 24 | PN | AU | | 0-0 | 21-52-41 | D08050P | | 37 | | TB0166F | A016 | 2 | | ALL |
| 401Y | 24 | PN | AU | | 0-0 | 21-52-41 | D08050P | | 38 | | TB0166F | C016 | 2 | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0091 | 286T0091 | | | SATCOM ,E9-1 SHELF,LEFT | | | | | | | | | | | |
| 001 | 16 | | PA | | 2-9 | 23-25-11 | D06149P | 21 | | | TB0257H | 3 | 2 | | 156-157, 166-199, 277-299 |
| 002 | 20 | | PA | | 2-8 | 23-25-11 | D02647C | 1 | | | TB0257H | 3 | 2 | | 156-157, 166-199, 277-299 |
| 003 | 20 | | PA | | 2-6 | 23-25-11 | D02647C | 8 | | | GDX0003 | D.. | 2 | | 156-157, 166-199, 277-299 |
| 004 | 20 | | PA | | 2-6 | 23-25-11 | D02647C | 7 | | | GDX0003 | A.. | 2 | | 156-157, 166-199, 277-299 |
| 005 | 24 | | PK | | 3-0 | 23-25-11 | D02647B | G05 | | | D06161P | 3 | | | 167-199, 277-299 |
| 006 | 24 | | PK | | 3-0 | 23-25-11 | D02647B | A05 | | | D06161P | 4 | | | 167-199, 277-299 |
| 007 | 20 | | PA | | 3-5 | 23-25-11 | D06161P | 1 | | | TB0257H | 3 | 2 | | 167-199, 277-299 |
| 008 | 20 | | PA | | 3-5 | 23-25-11 | D06161P | 2 | | | TB0257H | 3 | 2 | | 167-199, 277-299 |
| 009 | 16 | | PA | | 0-7 | 23-25-11 | D06149P | 23 | | | TB0257H | 1 | 2 | | 156-157, 166-199 |
| 009 | 16 | | PA | | 0-7 | 23-25-11 | TB0257H | 1 | 2 | | TB0257H | 3 | 2 | | 277-299 |
| 010 | 22 | | PA | | 2-6 | 23-25-14 | D02647B | C14 | | | GDX0003 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 011 | 24 | | PK | | 2-4 | 23-25-14 | D06149P | 25 | | | D02647B | B14 | | | 156-157, 166-199, 277-299 |
| 012 | 24 | | PV | AL | 2-4 | 23-25-14 | D06149P | 27 | | | D02647B | A02 | | | 156-157, 166-199, 277-299 |
| 012Z | | | | AL | 0-0 | 23-25-14 | D06149P | 26 | | | D02647B | B02 | | | 156-157, 166-199, 277-299 |
| 013 | 24 | | PV | AM | 2-4 | 23-25-14 | D06149P | 29 | | | D02647B | C02 | | | 156-157, 166-199, 277-299 |
| 013Z | | | | AM | 0-0 | 23-25-14 | D06149P | 28 | | | D02647B | D02 | | | 156-157, 166-199, 277-299 |
| 014 | 24 | | PK | | 2-4 | 23-25-14 | D06149P | 30 | | | D02647B | E08 | | | 156-157, 166-199, 277-299 |
| 015 | 24 | | PK | | 2-4 | 23-25-14 | D06149P | 31 | | | D02647B | F08 | | | 156-157, 166-199, 277-299 |
| 016 | 24 | | PV | AP | 2-2 | 23-25-14 | D02647B | G02 | | | TB0257F | C021 | 2 | | 156-157, 166-199, 277-299 |
| 016Z | | | | AP | 0-0 | 23-25-14 | D02647B | H02 | | | TB0257F | A021 | 2 | | 156-157, 166-199, 277-299 |
| 017 | 24 | | PV | AQ | 2-2 | 23-25-14 | D02647B | E02 | | | TB0257F | C023 | 2 | | 156-157, 166-199, 277-299 |
| 017Z | | | | AQ | 0-0 | 23-25-14 | D02647B | F02 | | | TB0257F | A023 | 2 | | 156-157, 166-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0090
Page 1
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0091 | 286T0091 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | | |
| 018 | 24 | | PK | 2-2 | 23-25-14 | D02647B | G08 | | | | TB0257F | A025 | 2 | | 156-157, 166-199, 277-299 | |
| 019 | 24 | | PK | 2-2 | 23-25-14 | D02647B | H08 | | | | TB0257F | C025 | 2 | | 156-157, 166-199, 277-299 | |
| 021 | 20 | | PA | 2-10 | 23-25-16 | D06165P | | 13 | | | TB0257H | | 1 | 2 | 156-157, 166-199, 277-299 | |
| 022 | 20 | | PA | 2-10 | 23-25-16 | D06165P | | 14 | | | TB0257H | | 1 | 2 | 156-157, 166-199, 277-299 | |
| 024 | 20 | | PA | 3-7 | 23-25-17 | D06173P | | 1 | | | TB0257H | | 1 | 2 | 156-157, 166-199, 277-299 | |
| 025 | 20 | | PA | 3-7 | 23-25-17 | D06173P | | 4 | | | TB0257H | | 1 | 2 | 156-157, 166-199, 277-299 | |
| 026 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | C13 | | | D02701 | | 1 | | 156-157, 166-199, 277-299 | |
| 027 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | D13 | | | D02701 | | 2 | | 280-299 | |
| 028 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | E13 | | | D02701 | | 3 | | 156-157, 166-199, 277-299 | |
| 029 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | F13 | | | D02701 | | 4 | | 156-157, 166-199, 277-299 | |
| 030 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | G13 | | | D02701 | | 5 | | 156-157, 166-199, 280-299 | |
| 031 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | H13 | | | D02701 | | 6 | | 277-299 | |
| 032 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | J13 | | | D02701 | | 7 | | 166, 277-299 | |
| 033 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | K13 | | | D02701 | | 8 | | 277-299 | |
| 034 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | D14 | | | D02701 | | 9 | | 277-299 | |
| 035 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | E14 | | | D02701 | | 10 | | 156-157, 166-199, 280-299 | |
| 036 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | F14 | | | D02701 | | 11 | | 156-157, 167-199, 277-299 | |
| 037 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | G14 | | | D02701 | | 12 | | 156-157, 166-199, 277-299 | |
| 038 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | H14 | | | D02701 | | 13 | | 156-157, 167-199, 277-299 | |
| 039 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | J14 | | | D02701 | | 14 | | 156-157, 167-199, 277-299 | |
| 040 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | K14 | | | D02701 | | 15 | | 156-157, 166-199, 277-299 | |
| 041 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | A15 | | | D02701 | | 16 | | 156-157, 166-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W0090

Page 2

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0091 | 286T0091 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | |
| 042 | 24 | | PK | | 2-9 | 23-25-15 | D02647B | | B15 | | D02701 | | 17 | | 156-157, 167-199, 277-299 |
| 043 | 24 | | PK | | 2-9 | 23-25-15 | D02647B | | C15 | | D02701 | | 18 | | 156-157, 166, 280-299 |
| 044 | 24 | | PK | | 2-9 | 23-25-15 | D02647B | | D15 | | D02701 | | 19 | | 166-199, 277-299 |
| 045 | 24 | | PK | | 2-9 | 23-25-15 | D02647B | | E15 | | D02701 | | 20 | | 166-199, 277-299 |
| 046 | 24 | | PK | | 2-9 | 23-25-15 | D02647B | | F15 | | D02701 | | 21 | | 156-157, 277, 280-299 |
| 047 | 24 | | PK | | 2-9 | 23-25-15 | D02647B | | G15 | | D02701 | | 22 | | 156-157, 278-299 |
| 048 | 24 | | PK | | 2-9 | 23-25-15 | D02647B | | H15 | | D02701 | | 23 | | 156, 166-199, 277-299 |
| 049 | 24 | | PK | | 2-9 | 23-25-15 | D02647B | | J15 | | D02701 | | 24 | | 157, 167-199, 278-299 |
| 050 | 24 | | PK | | 2-9 | 23-25-15 | D02647B | | K15 | | D02701 | | 25 | | 156-157, 166-199, 277-299 |
| 051 | 20 | | PA | | 3-1 | 23-25-17 | D06171P | | | 14 | TB0257H | | 1 | 2 | 156-157, 166-199, 277-299 |
| 052 | 20 | | PA | | 3-1 | 23-25-17 | D06171P | | | 15 | TB0257H | | 1 | 2 | 156-157, 166-199, 277-299 |
| 053 | 20 | | PA | | 2-0 | 23-25-12 | D02649C | | | 1 | TB0257H | | 3 | 2 | 156-157, 166-199 |
| 053 | 20 | | PA | | 2-0 | 23-25-12 | D02649C | | | 1 | TB0257H | | 1 | 2 | 277-299 |
| 054 | 18 | | PA | | 2-6 | 23-25-12 | D02649C | | | 7 | GDX0002 | | A.. | 2 | 156-157, 166-199, 277-299 |
| 055 | 18 | | PA | | 2-6 | 23-25-12 | D02649C | | | 8 | GDX0002 | | S.. | 2 | 156-157, 166-199, 277-299 |
| 057 | 24 | | PK | | 4-8 | 23-25-15 | D02701 | | | 27 | D06253J | | 16 | | 167-199 |
| 058 | 20 | | PA | | 4-1 | 23-25-15 | GDX0004 | | A.. | 2 | D06253J | | 17 | | 167-199 |
| 059 | 20 | | PA | | 4-1 | 23-25-15 | GDX0004 | | D.. | 2 | D06253J | | 18 | | 167-199 |
| 060 | 24 | | PK | | 4-1 | 23-25-15 | D02647B | | E11 | | D06253J | | 1 | | 167-199 |
| 061 | 24 | | PK | | 4-1 | 23-25-15 | D02647B | | G11 | | D06253J | | 2 | | 167-199 |
| 062 | 24 | | PK | | 4-1 | 23-25-15 | D02647B | | H11 | | D06253J | | 3 | | 167-199 |
| 063 | 24 | | PK | | 4-1 | 23-25-15 | D02647B | | J11 | | D06253J | | 4 | | 167-199 |
| 064 | 24 | | PK | | 4-1 | 23-25-15 | D02647B | | K11 | | D06253J | | 5 | | 167-199 |
| 065 | 24 | | PK | | 4-1 | 23-25-15 | D02647A | | A15 | | D06253J | | 6 | | 167-199 |
| 066 | 24 | | PK | | 4-1 | 23-25-15 | D02647A | | B15 | | D06253J | | 7 | | 167-199 |
| 068 | 20 | | PA | | 4-6 | 23-25-15 | TB0257H | | | 3 | D06253J | | 9 | | 167-199 |
| 069 | 20 | | PA | | 2-5 | 23-25-16 | D02719C | | | 2 | TB0257H | | CAP | Y | 167-199 |
| 070 | 20 | | PA | | 2-10 | 23-25-16 | D02719C | | | 4 | GDX0004 | | A.. | 2 | 167-199 |
| 071 | 20 | | PA | | 2-10 | 23-25-16 | D02719C | | | 3 | GDX0004 | | S.. | 2 | 167-199 |
| 082 | 24 | | PK | | 2-9 | 23-25-15 | D02647A | | C11 | | D02701 | | 32 | | 156-157, 166-199 |
| 086 | 24 | | PK | | 2-9 | 23-25-15 | D02647A | | F13 | | D02701 | | 36 | | 156-157, 166-199 |
| 087 | 24 | | PK | | 2-9 | 23-25-15 | D02647A | | H13 | | D02701 | | 37 | | 156-157, 166-199 |
| 088 | 24 | | PK | | 2-9 | 23-25-15 | D02647A | | J12 | | D02701 | | 38 | | 156-157, 166-199 |

WIRE LIST

D280T132

91-21-11

Section W0090

Page 3

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0091 | 286T0091 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | | | |
| 089 | 24 | | PK | | 2-9 | 23-25-15 | D02647A | | K12 | | | | D02701 | 39 | | | 156-157, 166-199 |
| 100 | 22 | | PA | | 2-4 | 23-25-13 | D02647B | | CAP | Y | | | D06149P | 13 | | | 156-157, 166-199 |
| 100 | 24 | | PK | | 2-4 | 23-25-13 | D02647B | | A13 | | | | D06149P | 13 | | | 277-299 |
| 201B | 24 | | PW | IA | 2-9 | 23-25-11 | D06149P | | 4 | | | | TB0257H | 7 | 2 | | 156-157, 166, 277-299 |
| 201B | 24 | | PW | IA | 3-0 | 23-25-11 | D06149P | | 4 | | | | TB0257H | 7 | # | | 167-199 |
| 201R | 24 | | PW | IA | 0-0 | 23-25-11 | D06149P | | 6 | | | | TB0257H | 5 | 2 | | 156-157, 166, 277-299 |
| 201R | 24 | | PW | IA | 0-0 | 23-25-11 | D06149P | | 6 | | | | TB0257H | 5 | # | | 167-199 |
| 201Z | | | | IA | 0-0 | 23-25-11 | D06149P | | 5 | | | | GDX0001 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 203B | 24 | | PW | IC | 3-5 | 23-25-11 | D06161P | | 7 | | | | TB0257H | 7 | 2 | | 277-299 |
| 203R | 24 | | PW | IC | 0-0 | 23-25-11 | D06161P | | 6 | | | | TB0257H | 5 | 2 | | 277-299 |
| 203Z | | | | IC | 0-0 | 23-25-11 | D06161P | | 5 | | | | GDX0001 | S.. | 2 | | 277-299 |
| 204B | 24 | | PW | ID | 2-8 | 23-25-11 | D02647B | | H04 | | | | TB0257H | 7 | 2 | | 156-157, 166-199, 277-299 |
| 204R | 24 | | PW | ID | 0-0 | 23-25-11 | D02647B | | G04 | | | | TB0257H | 5 | 2 | | 156-157, 166-199, 277-299 |
| 204Z | | | | ID | 0-0 | 23-25-11 | D02647B | | DED | | | | GDX0001 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 205 | 20 | | UA | | 1-6 | 23-25-11 | D02647B | | REF | | IE | | GDX0003 | S.. | 2 | | 277-299 |
| 205B | 24 | | PW | IE | 3-0 | 23-25-11 | D02647B | | K06 | | | | D06161P | 9 | | | 277-299 |
| 205R | 24 | | PW | IE | 0-0 | 23-25-11 | D02647B | | J06 | | | | D06161P | 8 | | | 277-299 |
| 205Z | | | | IE | 0-0 | 23-25-11 | D02647B | | REF | | IE | | D06161P | 10 | | | 277-299 |
| 206 | 20 | | UA | | 1-6 | 23-25-12 | D02649A | | REF | | IF | | GDX0001 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 206B | 24 | | PW | IF | 2-10 | 23-25-12 | D02647B | | F09 | | | | D02649A | B01 | | | 156-157, 166-199, 277-299 |
| 206R | 24 | | PW | IF | 0-0 | 23-25-12 | D02647B | | E09 | | | | D02649A | A01 | | | 156-157, 166-199, 277-299 |
| 206Z | | | | IF | 0-0 | 23-25-12 | D02647B | | DED | | | | D02649A | REF | | IF | 156-157, 166-199, 277-299 |
| 207 | 20 | | UA | | 1-6 | 23-25-12 | D02649A | | REF | | IG | | GDX0001 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 207B | 24 | | PW | IG | 2-10 | 23-25-12 | D02647B | | H09 | | | | D02649A | D01 | | | 156-157, 166-199, 277-299 |
| 207R | 24 | | PW | IG | 0-0 | 23-25-12 | D02647B | | G09 | | | | D02649A | C01 | | | 156-157, 166-199, 277-299 |
| 207Z | | | | IG | 0-0 | 23-25-12 | D02647B | | DED | | | | D02649A | REF | | IG | 156-157, 166-199, 277-299 |
| 208 | 20 | | UA | | 1-6 | 23-25-12 | D02649A | | REF | | IH | | GDX0001 | S.. | 2 | | 156-157, 166-199 |

WIRE LIST

D280T132

91-21-11

Section W0090

Page 4

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|--|-------|-------------|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0091 | 286T0091 | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | | | |
| 208 | 20 | UA | | | 1-6 | 23-25-12 | D02649B | REF | | IH | GDX0001 | S.. | 2 | | 277-299 |
| 208B | 24 | PW | IH | | 2-10 | 23-25-12 | D02647B | K09 | | | D02649A | F01 | | | 156-157, 166-199 |
| 208B | 24 | PW | IH | | 2-10 | 23-25-12 | D02647B | K09 | | | D02649B | F01 | | | 277-299 |
| 208R | 24 | PW | IH | | 0-0 | 23-25-12 | D02647B | J09 | | | D02649A | E01 | | | 156-157, 166-199 |
| 208R | 24 | PW | IH | | 0-0 | 23-25-12 | D02647B | J09 | | | D02649B | E01 | | | 277-299 |
| 208Z | | | IH | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | IH | 156-157, 166-199 |
| 208Z | | | IH | | 0-0 | 23-25-12 | D02647B | DED | | | D02649B | REF | | IH | 277-299 |
| 209 | 20 | UA | | | 1-6 | 23-25-12 | D02649A | REF | | II | GDX0001 | S.. | 2 | | 156-157, 166-199 |
| 209 | 20 | UA | | | 1-6 | 23-25-12 | D02649B | REF | | II | GDX0001 | S.. | 2 | | 277-299 |
| 209B | 24 | PW | II | | 2-10 | 23-25-12 | D02647B | B10 | | | D02649A | H01 | | | 156-157, 166-199 |
| 209B | 24 | PW | II | | 2-10 | 23-25-12 | D02647B | B10 | | | D02649B | H01 | | | 277-299 |
| 209R | 24 | PW | II | | 0-0 | 23-25-12 | D02647B | A10 | | | D02649A | G01 | | | 156-157, 166-199 |
| 209R | 24 | PW | II | | 0-0 | 23-25-12 | D02647B | A10 | | | D02649B | G01 | | | 277-299 |
| 209Z | | | II | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | II | 156-157, 166-199 |
| 209Z | | | II | | 0-0 | 23-25-12 | D02647B | DED | | | D02649B | REF | | II | 277-299 |
| 210 | 20 | UA | | | 1-6 | 23-25-12 | D02649A | REF | | IJ | GDX0001 | S.. | 2 | | 156-157, 166-199 |
| 210 | 20 | UA | | | 1-6 | 23-25-12 | D02649B | REF | | IJ | GDX0001 | S.. | 2 | | 277-299 |
| 210B | 24 | PW | IJ | | 2-10 | 23-25-12 | D02647B | D10 | | | D02649A | K01 | | | 156-157, 166-199 |
| 210B | 24 | PW | IJ | | 2-10 | 23-25-12 | D02647B | D10 | | | D02649B | K01 | | | 277-299 |
| 210R | 24 | PW | IJ | | 0-0 | 23-25-12 | D02647B | C10 | | | D02649A | J01 | | | 156-157, 166-199 |
| 210R | 24 | PW | IJ | | 0-0 | 23-25-12 | D02647B | C10 | | | D02649B | J01 | | | 277-299 |
| 210Z | | | IJ | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | IJ | 156-157, 166-199 |
| 210Z | | | IJ | | 0-0 | 23-25-12 | D02647B | DED | | | D02649B | REF | | IJ | 277-299 |
| 211 | 20 | UA | | | 1-6 | 23-25-12 | D02649A | REF | | IK | GDX0001 | S.. | 2 | | 156-157, 166-199 |
| 211 | 20 | UA | | | 1-6 | 23-25-12 | D02649B | REF | | IK | GDX0001 | S.. | 2 | | 277-299 |
| 211B | 24 | PW | IK | | 2-10 | 23-25-12 | D02647B | F10 | | | D02649A | B03 | | | 156-157, 166-199 |
| 211B | 24 | PW | IK | | 2-10 | 23-25-12 | D02647B | F10 | | | D02649B | B03 | | | 277-299 |
| 211R | 24 | PW | IK | | 0-0 | 23-25-12 | D02647B | E10 | | | D02649A | A03 | | | 156-157, 166-199 |
| 211R | 24 | PW | IK | | 0-0 | 23-25-12 | D02647B | E10 | | | D02649B | A03 | | | 277-299 |
| 211Z | | | IK | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | IK | 156-157, 166-199 |
| 211Z | | | IK | | 0-0 | 23-25-12 | D02647B | DED | | | D02649B | REF | | IK | 277-299 |
| 212 | 20 | UA | | | 1-6 | 23-25-12 | D02649A | REF | | IL | GDX0001 | S.. | 2 | | 156-157, 166-199 |
| 212 | 20 | UA | | | 1-6 | 23-25-12 | D02649B | REF | | IL | GDX0001 | S.. | 2 | | 277-299 |
| 212B | 24 | PW | IL | | 2-10 | 23-25-12 | D02647B | H10 | | | D02649A | D03 | | | 156-157, 166-199 |
| 212B | 24 | PW | IL | | 2-10 | 23-25-12 | D02647B | H10 | | | D02649B | D03 | | | 277-299 |
| 212R | 24 | PW | IL | | 0-0 | 23-25-12 | D02647B | G10 | | | D02649A | C03 | | | 156-157, 166-199 |
| 212R | 24 | PW | IL | | 0-0 | 23-25-12 | D02647B | G10 | | | D02649B | C03 | | | 277-299 |
| 212Z | | | IL | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | IL | 156-157, 166-199 |
| 212Z | | | IL | | 0-0 | 23-25-12 | D02647B | DED | | | D02649B | REF | | IL | 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0090

Page 5

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|---------|---------|------|------|------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0091 | 286T0091 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | |
| 213 | 20 | | UA | 1-6 | 23-25-12 | D02649A | REF | | IM | GDX0001 | S.. | 2 | | 156-157, 166-199 | |
| 213 | 20 | | UA | 1-6 | 23-25-12 | D02649B | REF | | IM | GDX0001 | S.. | 2 | | 277-299 | |
| 213B | 24 | | PW | IM | 2-10 | 23-25-12 | D02647B | K10 | | D02649A | F03 | | | 156-157, 166-199 | |
| 213B | 24 | | PW | IM | 2-10 | 23-25-12 | D02647B | K10 | | D02649B | F03 | | | 277-299 | |
| 213R | 24 | | PW | IM | 0-0 | 23-25-12 | D02647B | J10 | | D02649A | E03 | | | 156-157, 166-199 | |
| 213R | 24 | | PW | IM | 0-0 | 23-25-12 | D02647B | J10 | | D02649B | E03 | | | 277-299 | |
| 213Z | | | | IM | 0-0 | 23-25-12 | D02647B | DED | | D02649A | REF | | IM | 156-157, 166-199 | |
| 213Z | | | | IM | 0-0 | 23-25-12 | D02647B | DED | | D02649B | REF | | IM | 277-299 | |
| 216B | 24 | | PW | IP | 2-10 | 23-25-16 | D06165P | 18 | | TB0257H | 7 | 2 | | 156-157, 166-199, 277-299 | |
| 216R | 24 | | PW | IP | 0-0 | 23-25-16 | D06165P | 17 | | TB0257H | 5 | 2 | | 156-157, 166-199, 277-299 | |
| 216Z | | | | IP | 0-0 | 23-25-16 | D06165P | 19 | | GDX0001 | S.. | 2 | | 156-157, 166-199, 277-299 | |
| 217 | 20 | | UA | | 1-6 | 23-25-16 | D02647B | REF | | IQ | GDX0003 | S.. | 2 | 156-157, 166-199, 277-299 | |
| 217B | 24 | | PW | IQ | 2-5 | 23-25-16 | D02647B | F06 | | D06165P | 21 | | | 156-157, 166-199, 277-299 | |
| 217R | 24 | | PW | IQ | 0-0 | 23-25-16 | D02647B | E06 | | D06165P | 20 | | | 156-157, 166-199, 277-299 | |
| 217Z | | | | IQ | 0-0 | 23-25-16 | D02647B | REF | | IQ | D06165P | 22 | | 156-157, 166-199, 277-299 | |
| 218B | 24 | | PL | IR | 2-4 | 23-25-17 | D06171P | 2 | | TB0257G | 33 | 2 | | 156-157, 166-199, 277-299 | |
| 218R | 24 | | PL | IR | 0-0 | 23-25-17 | D06171P | 1 | | TB0257G | 31 | 2 | | 156-157, 166-199, 277-299 | |
| 219B | 24 | | PW | IS | 2-4 | 23-25-17 | D06171P | 4 | | TB0257G | 35 | 2 | | 156-157, 166-199, 277-299 | |
| 219R | 24 | | PW | IS | 0-0 | 23-25-17 | D06171P | 3 | | TB0257G | 34 | 2 | | 156-157, 166-199, 277-299 | |
| 219Z | | | | IS | 0-0 | 23-25-17 | D06171P | 5 | | GDX0003 | S.. | 2 | | 156-157, 166-199, 277-299 | |
| 220B | 24 | | PW | IT | 2-9 | 23-25-17 | D06171P | 7 | | TB0257G | 29 | 2 | | 156-157, 166-199, 277-299 | |
| 220R | 24 | | PW | IT | 0-0 | 23-25-17 | D06171P | 6 | | TB0257G | 27 | 2 | | 156-157, 166-199, 277-299 | |
| 220Z | | | | IT | 0-0 | 23-25-17 | D06171P | 8 | | GDX0003 | S.. | 2 | | 156-157, 166-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W0090

Page 6

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|------|--|---------|-------|------|------|---------|---------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0091 | 286T0091 | | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | |
| 221B | 24 | PW | IU | 3-1 | 23-25-17 | D06171P | 10 | | | TB0257H | 7 | 2 | | 156-157, 166-199, 277-299 | | |
| 221R | 24 | PW | IU | 0-0 | 23-25-17 | D06171P | 9 | | | TB0257H | 5 | 2 | | 156-157, 166-199, 277-299 | | |
| 221Z | | | IU | 0-0 | 23-25-17 | D06171P | 11 | | | GDX0001 | S.. | 2 | | 156-157, 166-199, 277-299 | | |
| 222B | 24 | PL | IV | 1-11 | 23-25-17 | D06171P | 13 | | | D06165P | 23 | | | 156-157, 166-199, 277-299 | | |
| 222R | 24 | PL | IV | 0-0 | 23-25-17 | D06171P | 12 | | | D06165P | 24 | | | 156-157, 166-199, 277-299 | | |
| 224B | 24 | PL | IX | 2-4 | 23-25-17 | D06165P | 26 | | | D06173P | 2 | | | 156-157, 166-199, 277-299 | | |
| 224R | 24 | PL | IX | 0-0 | 23-25-17 | D06165P | 25 | | | D06173P | 3 | | | 156-157, 166-199, 277-299 | | |
| 225B | 24 | PW | IY | 3-7 | 23-25-17 | D06173P | 5 | | | TB0257H | 7 | 2 | | 156-157, 166-199, 277-299 | | |
| 225R | 24 | PW | IY | 0-0 | 23-25-17 | D06173P | 6 | | | TB0257H | 5 | 2 | | 156-157, 166-199, 277-299 | | |
| 225Z | | | IY | 0-0 | 23-25-17 | D06173P | 7 | | | GDX0001 | S.. | 2 | | 156-157, 166-199, 277-299 | | |
| 226B | 24 | PW | JA | 3-3 | 23-25-17 | D06173P | 8 | | | TB0257G | 29 | 2 | | 156-157, 166-199, 277-299 | | |
| 226R | 24 | PW | JA | 0-0 | 23-25-17 | D06173P | 9 | | | TB0257G | 27 | 2 | | 156-157, 166-199, 277-299 | | |
| 226Z | | | JA | 0-0 | 23-25-17 | D06173P | 10 | | | GDX0003 | S.. | 2 | | 156-157, 166-199, 277-299 | | |
| 227B | 24 | PW | JB | 2-10 | 23-25-17 | D06173P | 11 | | | TB0257G | 35 | 2 | | 156-157, 166-199, 277-299 | | |
| 227R | 24 | PW | JB | 0-0 | 23-25-17 | D06173P | 12 | | | TB0257G | 34 | 2 | | 156-157, 166-199, 277-299 | | |
| 227Z | | | JB | 0-0 | 23-25-17 | D06173P | 13 | | | GDX0003 | S.. | 2 | | 156-157, 166-199, 277-299 | | |
| 228B | 24 | PL | JC | 2-10 | 23-25-17 | D06173P | 14 | | | TB0257G | 33 | 2 | | 156-157, 166-199, 277-299 | | |
| 228R | 24 | PL | JC | 0-0 | 23-25-17 | D06173P | 15 | | | TB0257G | 31 | 2 | | 156-157, 166-199, 277-299 | | |
| 229 | 20 | UA | | 1-6 | 23-25-13 | D02647B | | | | JD | GDX0003 | S.. | 2 | 156-157, 166-199, 277-299 | | |

WIRE LIST
D280T132

91-21-11
Section W0090
Page 7
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|--|---------|-------|------|------|---------|-------|------|------|--------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0091 | 286T0091 | | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | |
| 229B | 24 | PW | JD | 2-4 | 23-25-13 | D02647B | H01 | | | D06149P | 3 | | | | 156-157, 166-199, 277-299 | |
| 229R | 24 | PW | JD | 0-0 | 23-25-13 | D02647B | G01 | | | D06149P | 2 | | | | 156-157, 166-199, 277-299 | |
| 229Z | | | JD | 0-0 | 23-25-13 | D02647B | | | JD | D06149P | 1 | | | | 156-157, 166-199, 277-299 | |
| 230 | 20 | UA | | 1-6 | 23-25-13 | D02647B | | | JE | GDX0003 | S.. | 2 | | | 156-157, 166-199, 277-299 | |
| 230B | 24 | PW | JE | 2-4 | 23-25-13 | D02647B | K01 | | | D06149P | 34 | | | | 156-157, 166-199, 277-299 | |
| 230R | 24 | PW | JE | 0-0 | 23-25-13 | D02647B | J01 | | | D06149P | 33 | | | | 156-157, 166-199, 277-299 | |
| 230Z | | | JE | 0-0 | 23-25-13 | D02647B | | | JE | D06149P | 32 | | | | 156-157, 166-199, 277-299 | |
| 231 | 20 | UA | | 1-6 | 23-25-13 | D02647B | | | JF | GDX0003 | S.. | 2 | | | 156-157, 166-199, 277-299 | |
| 231B | 24 | PW | JF | 2-4 | 23-25-13 | D02647B | H12 | | | D06149P | 12 | | | | 156-157, 166-199, 277-299 | |
| 231R | 24 | PW | JF | 0-0 | 23-25-13 | D02647B | G12 | | | D06149P | 11 | | | | 156-157, 166-199, 277-299 | |
| 231Z | | | JF | 0-0 | 23-25-13 | D02647B | | | JF | D06149P | 10 | | | | 156-157, 166-199, 277-299 | |
| 232 | 20 | UA | | 1-6 | 23-25-13 | D02647B | | | JG | GDX0002 | S.. | 2 | | | 156-157, 166 | |
| 232 | 20 | UA | | 1-6 | 23-25-13 | D02647B | | | JG | GDX0003 | S.. | 2 | | | 277-299 | |
| 232B | 24 | PW | JG | 2-4 | 23-25-13 | D02647B | D03 | | | D06149P | 16 | | | | 156-157, 166, 277-299 | |
| 232B | 24 | PW | JG | 2-6 | 23-25-13 | TB0257G | 14 | 2 | | D06149P | 16 | | | | 167-199 | |
| 232R | 24 | PW | JG | 0-0 | 23-25-13 | D02647B | C03 | | | D06149P | 15 | | | | 156-157, 166, 277-299 | |
| 232R | 24 | PW | JG | 0-0 | 23-25-13 | TB0257G | 13 | 2 | | D06149P | 15 | | | | 167-199 | |
| 232Z | | | JG | 0-0 | 23-25-13 | D02647B | | | JG | D06149P | 14 | | | | 156-157, 166, 277-299 | |
| 232Z | | | JG | 0-0 | 23-25-13 | GDX0002 | S.. | 2 | | D06149P | 14 | | | | 167-199 | |
| 233 | 20 | UA | | 1-6 | 23-25-13 | D02647B | | | JH | GDX0003 | S.. | 2 | | | 156-157, 166-199, 277-299 | |
| 233B | 24 | PW | JH | 2-4 | 23-25-13 | D02647B | B06 | | | D06149P | 19 | | | | 156-157, 166-199, 277-299 | |
| 233R | 24 | PW | JH | 0-0 | 23-25-13 | D02647B | A06 | | | D06149P | 18 | | | | 156-157, 166-199, 277-299 | |
| 233Z | | | JH | 0-0 | 23-25-13 | D02647B | | | JH | D06149P | 17 | | | | 156-157, 166-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W0090

Page 8

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0091 | 286T0091 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | |
| 234B | 24 | PW | JI | 2-8 | 23-25-13 | D06149P | 24 | | | TB0257G | 12 | 2 | | 156-157, 166-199, 277-299 | |
| 234R | 24 | PW | JI | 0-0 | 23-25-13 | D06149P | 22 | | | TB0257G | 11 | 2 | | 156-157, 166-199, 277-299 | |
| 234Z | | | JI | 0-0 | 23-25-13 | D06149P | 20 | | | GDX0002 | S.. | 2 | | 156-157, 166-199, 277-299 | |
| 235B | 24 | PW | JJ | 2-6 | 23-25-13 | D02647B | K03 | | | TB0257G | 12 | 2 | | 156-157, 166-199, 277-299 | |
| 235R | 24 | PW | JJ | 0-0 | 23-25-13 | D02647B | J03 | | | TB0257G | 11 | 2 | | 156-157, 166-199, 277-299 | |
| 235Z | | | JJ | 0-0 | 23-25-13 | D02647B | DED | | | GDX0002 | S.. | 2 | | 156-157, 166-199, 277-299 | |
| 236B | 24 | PW | JK | 2-4 | 23-25-13 | D02647B | K12 | | | TB0257F | C015 | 2 | | 156-157, 166-199, 277-299 | |
| 236R | 24 | PW | JK | 0-0 | 23-25-13 | D02647B | J12 | | | TB0257F | A015 | 2 | | 156-157, 166-199, 277-299 | |
| 236Z | | | JK | 0-0 | 23-25-13 | D02647B | DED | | | GDX0002 | S.. | 2 | | 156-157, 166-199, 277-299 | |
| 237B | 24 | PW | JL | 2-5 | 23-25-13 | D02647B | D06 | | | TB0257F | C019 | 2 | | 277-299 | |
| 237R | 24 | PW | JL | 0-0 | 23-25-13 | D02647B | C06 | | | TB0257F | A019 | 2 | | 277-299 | |
| 237Z | | | JL | 0-0 | 23-25-13 | D02647B | DED | | | GDX0002 | S.. | 2 | | 277-299 | |
| 238B | 24 | PL | JM | 2-2 | 23-25-17 | D02647B | CAP | Y | | TB0257G | 33 | 2 | | 156-157, 166-199, 277-299 | |
| 238R | 24 | PL | JM | 0-0 | 23-25-17 | D02647B | CAP | Y | | TB0257G | 31 | 2 | | 156-157, 166-199, 277-299 | |
| 239B | 24 | PW | JN | 2-2 | 23-25-17 | D02647B | CAP | Y | | TB0257G | 35 | 2 | | 156-157, 166-199, 277-299 | |
| 239R | 24 | PW | JN | 0-0 | 23-25-17 | D02647B | CAP | Y | | TB0257G | 34 | 2 | | 156-157, 166-199, 277-299 | |
| 239Z | | | JN | 0-0 | 23-25-17 | D02647B | DED | | | GDX0003 | S.. | 2 | | 156-157, 166-199, 277-299 | |
| 240B | 24 | PW | JO | 2-4 | 23-25-17 | D02647B | CAP | Y | | TB0257G | 29 | 2 | | 156-157, 166-199, 277-299 | |
| 240R | 24 | PW | JO | 0-0 | 23-25-17 | D02647B | CAP | Y | | TB0257G | 27 | 2 | | 156-157, 166-199, 277-299 | |
| 240Z | | | JO | 0-0 | 23-25-17 | D02647B | DED | | | GDX0003 | S.. | 2 | | 156-157, 166-199, 277-299 | |
| 241B | 24 | PW | JP | 2-4 | 23-25-13 | TB0257G | 14 | 2 | | D02647B | D03 | | | 167-199 | |
| 241R | 24 | PW | JP | 0-0 | 23-25-13 | TB0257G | 13 | 2 | | D02647B | C03 | | | 167-199 | |

WIRE LIST

D280T132

91-21-11
Section W0090
Page 9
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|----|--|----------|----------|---------|-----|-----|-------|---------|---------|------|------|--------|-------|------------------|
| | | | | | Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term |
| W0091 | 286T0091 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | | | |
| 241Z | | | | JP | 0-0 | 23-25-13 | D02647B | DED | | | | GDX0002 | S.. | 2 | | | 167-199 |
| 242B | 24 | PW | JQ | | 4-3 | 23-25-15 | TB0257G | 14 | 2 | | | D06253J | 11 | | | | 167-199 |
| 242R | 24 | PW | JQ | | 0-0 | 23-25-15 | TB0257G | 13 | 2 | | | D06253J | 10 | | | | 167-199 |
| 242Z | | | | JQ | 0-0 | 23-25-15 | GDX0002 | S.. | 2 | | | D06253J | 12 | | | | 167-199 |
| 243B | 24 | PW | JR | | 4-5 | 23-25-15 | TB0257G | 12 | 2 | | | D06253J | 14 | | | | 167-199 |
| 243R | 24 | PW | JR | | 0-0 | 23-25-15 | TB0257G | 11 | 2 | | | D06253J | 13 | | | | 167-199 |
| 243Z | | | | JR | 0-0 | 23-25-15 | GDX0002 | S.. | 2 | | | D06253J | 15 | | | | 167-199 |
| 244 | 20 | UA | | | 1-6 | 23-25-16 | D02719A | REF | | JS | | GDX0004 | S.. | 2 | | | 167-199 |
| 244B | 24 | PW | JS | | 2-8 | 23-25-16 | D02719A | B04 | | | | D06165P | 2 | | | | 167-199 |
| 244R | 24 | PW | JS | | 0-0 | 23-25-16 | D02719A | A04 | | | | D06165P | 1 | | | | 167-199 |
| 244Z | | | | JS | 0-0 | 23-25-16 | D02719A | REF | | JS | | D06165P | 3 | | | | 167-199 |
| 245 | 20 | UA | | | 1-6 | 23-25-16 | D02719A | REF | | JT | | GDX0004 | S.. | 2 | | | 167-199 |
| 245B | 24 | PW | JT | | 2-8 | 23-25-16 | D02719A | B06 | | | | D06165P | 5 | | | | 167-199 |
| 245R | 24 | PW | JT | | 0-0 | 23-25-16 | D02719A | A06 | | | | D06165P | 4 | | | | 167-199 |
| 245Z | | | | JT | 0-0 | 23-25-16 | D02719A | REF | | JT | | D06165P | 6 | | | | 167-199 |
| 246B | 22 | PB | JU | | 2-8 | 23-25-16 | D02719A | B01 | | | | D06165P | 34 | | | | 167-199 |
| 246R | 22 | PB | JU | | 0-0 | 23-25-16 | D02719A | B02 | | | | D06165P | 33 | | | | 167-199 |
| 247B | 24 | PL | JV | | 2-8 | 23-25-16 | D02719A | B14 | | | | D06165P | 16 | | | | 167-199 |
| 247R | 24 | PL | JV | | 0-0 | 23-25-16 | D02719A | A14 | | | | D06165P | 15 | | | | 167-199 |
| 248B | 24 | PW | JW | | 2-5 | 23-25-16 | D02719A | D11 | | | | TB0257H | 7 | 2 | | | 167-199 |
| 248R | 24 | PW | JW | | 0-0 | 23-25-16 | D02719A | C11 | | | | TB0257H | 5 | 2 | | | 167-199 |
| 248Z | | | | JW | 0-0 | 23-25-16 | D02719A | DED | | | | GDX0001 | S.. | 2 | | | 167-199 |
| 249 | 20 | UA | | | 1-6 | 23-25-16 | D02647B | REF | | JX | | GDX0004 | S.. | 2 | | | 167-199 |
| 249B | 24 | PW | JX | | 2-6 | 23-25-16 | D02719A | D15 | | | | D02647B | H07 | | | | 167-199 |
| 249R | 24 | PW | JX | | 0-0 | 23-25-16 | D02719A | C15 | | | | D02647B | G07 | | | | 167-199 |
| 249Z | | | | JX | 0-0 | 23-25-16 | D02719A | DED | | | | D02647B | REF | | JX | | 167-199 |
| 250 | 20 | UA | | | 1-6 | 23-25-16 | D02647B | REF | | JY | | GDX0004 | S.. | 2 | | | 167-199 |
| 250B | 24 | PW | JY | | 2-6 | 23-25-16 | D02719A | B11 | | | | D02647B | F07 | | | | 167-199 |
| 250R | 24 | PW | JY | | 0-0 | 23-25-16 | D02719A | A11 | | | | D02647B | E07 | | | | 167-199 |
| 250Z | | | | JY | 0-0 | 23-25-16 | D02719A | DED | | | | D02647B | REF | | JY | | 167-199 |
| 251 | 20 | UA | | | 1-6 | 23-25-15 | D02647B | REF | | KA | | GDX0004 | S.. | 2 | | | 167-199 |
| 251B | 24 | PW | KA | | 4-1 | 23-25-15 | D02647B | F04 | | | | D06253J | 20 | | | | 167-199 |
| 251R | 24 | PW | KA | | 0-0 | 23-25-15 | D02647B | E04 | | | | D06253J | 19 | | | | 167-199 |
| 251Z | | | | KA | 0-0 | 23-25-15 | D02647B | REF | | KA | | D06253J | 21 | | | | 167-199 |
| 301B | 24 | PM | MA | | 2-8 | 23-25-16 | D02719A | C10 | | | | D06165P | 12 | | | | 167-199 |
| 301R | 24 | PM | MA | | 0-0 | 23-25-16 | D02719A | D10 | | | | D06165P | 11 | | | | 167-199 |
| 301Y | 24 | PM | MA | | 0-0 | 23-25-16 | D02719A | B10 | | | | D06165P | 10 | | | | 167-199 |
| 901 | 22 | PA | | | 2-4 | 23-25-13 | D02647B | A08 | | | | D06149P | 35 | | | | 156-157, 166-199 |
| 902 | 20 | PA | | | 1-6 | 23-25-13 | D02647B | | | SL | | GDX0002 | S.. | 2 | | | 156-157, 166-199 |

WIRE LIST

D280T132

91-21-11

Section W0090

Page 10

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0091 | 286T0091 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | |
| 902B | 22 | PR | SL | 2-4 | 23-25-13 | D02647B | C07 | | | D06149P | 36 | | | 156-157, 166-199 | |
| 902R | 22 | PR | SL | 0-0 | 23-25-13 | D02647B | D07 | | | D06149P | 37 | | | 156-157, 166-199 | |
| 902Z | | | SL | 0-0 | 23-25-13 | D02647B | | | SL | D06149P | 38 | | | 156-157, 166-199 | |
| 904 | 20 | PA | | 1-6 | 23-25-13 | D02647B | | | SG | GDX0002 | S.. | 2 | | 156-157, 166-199 | |
| 904B | 22 | PR | SG | 0-0 | 23-25-13 | D02647B | B07 | | | D06165P | 40 | | | 156-157, 166-199 | |
| 904R | 22 | PR | SG | 2-4 | 23-25-13 | D02647B | A07 | | | D06165P | 39 | | | 156-157, 166-199 | |
| 904Z | | | SG | 0-0 | 23-25-13 | D02647B | | | SG | D06165P | 41 | | | 156-157, 166-199 | |
| 906 | 20 | PA | | 1-6 | 23-25-13 | D02647B | | | AT | GDX0003 | S.. | 2 | | 156-157, 166-199 | |
| 906B | 22 | PR | AT | 0-0 | 23-25-13 | D02647B | F03 | | | D06155P | 8 | | | 156-157, 166-199 | |
| 906R | 22 | PR | AT | 2-4 | 23-25-13 | D02647B | E03 | | | D06155P | 7 | | | 156-157, 166-199 | |
| 906Z | | | AT | 0-0 | 23-25-13 | D02647B | | | AT | D06155P | 6 | | | 156-157, 166-199 | |
| 908 | 20 | PA | | 1-6 | 23-25-14 | D02647B | | | SN | GDX0002 | S.. | 2 | | 156-157, 166-199 | |
| 908B | 22 | PR | SN | 0-0 | 23-25-14 | D02647B | K02 | | | D06173P | 20 | | | 156-157, 166-199 | |
| 908R | 22 | PR | SN | 2-4 | 23-25-14 | D02647B | J02 | | | D06173P | 19 | | | 156-157, 166-199 | |
| 908Z | | | SN | 0-0 | 23-25-14 | D02647B | | | SN | D06173P | 21 | | | 156-157, 166-199 | |
| 909 | 20 | PA | | 1-6 | 23-25-14 | D02647B | | | SB | GDX0002 | S.. | 2 | | 156-157, 166-199 | |
| 909B | 22 | PR | SB | 0-0 | 23-25-14 | D02647B | B03 | | | D06173P | 23 | | | 156-157, 166-199 | |
| 909R | 22 | PR | SB | 2-4 | 23-25-14 | D02647B | A03 | | | D06173P | 22 | | | 156-157, 166-199 | |
| 909Z | | | SB | 0-0 | 23-25-14 | D02647B | | | SB | D06173P | 24 | | | 156-157, 166-199 | |
| 910 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 1 | | | D02647A | G01 | | | 156-157, 166-199 | |
| 911 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 2 | | | D02647A | J01 | | | 156-157, 166-199 | |
| 912 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 3 | | | D02647A | A03 | | | 156-157, 166-199 | |
| 913 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 4 | | | D02647A | B03 | | | 156-157, 166-199 | |
| 914 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 5 | | | D02647A | C03 | | | 156-157, 166-199 | |
| 915 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 6 | | | D02647A | D03 | | | 156-157, 166-199 | |
| 916 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 7 | | | D02647A | E03 | | | 156-157, 166-199 | |
| 917 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 8 | | | D02647A | H01 | | | 156-157, 166-199 | |
| 918 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 9 | | | D02647A | K01 | | | 156-157, 166-199 | |
| 919 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 10 | | | D02647B | A13 | | | 156-157, 166-199 | |
| 920 | 20 | PA | | 2-8 | 23-25-13 | D96101P | 11 | | | TB0257H | 9 | 2 | | 156-157, 166-199 | |
| 921 | 20 | PA | | 2-6 | 23-25-13 | D96101P | 12 | | | GDX0002 | D.. | 2 | | 156-157, 166-199 | |
| 922 | 20 | PA | | 2-4 | 23-25-13 | D06149P | 39 | | | TB0257H | 9 | 2 | | 156-157, 166-199 | |
| 925 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 13 | | | D02647A | A01 | | | 156-157, 166-199 | |
| 926 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 14 | | | D02647A | C01 | | | 156-157, 166-199 | |
| 927 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 15 | | | D02647A | D01 | | | 156-157, 166-199 | |
| 928 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 16 | | | D02647A | G15 | | | 156-157, 166-199 | |
| 929 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 17 | | | D02647A | K15 | | | 156-157, 166-199 | |
| 930 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 18 | | | D02647A | F15 | | | 156-157, 166-199 | |
| 931 | 22 | PA | | 2-4 | 23-25-13 | D96101P | 19 | | | D02647A | J15 | | | 156-157, 166-199 | |

WIRE LIST

D280T132

91-21-11

Section W0090

Page 11

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0091 | 286T0091 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | |
| 932 | 22 | | PA | 2-4 | 23-25-13 | D96101P | 20 | | | D02647A | H15 | | | 156-157, 166-199 | |
| 933 | 22 | | PA | 2-4 | 23-25-13 | D96101P | 21 | | | D02647A | C15 | | | 156-157, 166-199 | |
| 934 | 20 | | PA | 1-6 | 23-25-13 | D02647B | | | SS | GDX0002 | D.. | 2 | | 156-157, 166-199 | |
| 934B | 22 | | PR SK | 0-0 | 23-25-13 | D96101P | 23 | | | D02647B | B01 | | | 156-157, 166-199 | |
| 934R | 22 | | PR SK | 2-4 | 23-25-13 | D96101P | 22 | | | D02647B | A01 | | | 156-157, 166-199 | |
| 934Z | | | SK | 0-0 | 23-25-13 | D96101P | | | HW | D02647B | | | SS | 156-157, 166-199 | |
| 936B | 22 | | PR SD | 2-4 | 23-25-13 | D96101P | 25 | | | D02647B | D01 | | | 156-157, 166-199 | |
| 936R | 22 | | PR SD | 0-0 | 23-25-13 | D96101P | 24 | | | D02647B | C01 | | | 156-157, 166-199 | |
| 936Z | | | SD | 0-0 | 23-25-13 | D96101P | | | HW | D02647B | | | SS | 156-157, 166-199 | |
| 938 | 20 | | PA | 2-8 | 23-25-13 | D96101P | 26 | | | TB0257H | 9 | 2 | | 156-157, 166-199 | |
| 939 | 20 | | PA | 2-8 | 23-25-13 | D96101P | 27 | | | TB0257H | 3 | 2 | | 156-157, 166-199 | |
| 940 | 20 | | PA | 2-4 | 23-25-13 | D96101P | 28 | | | GDX0002 | D.. | 2 | | 156-157, 166-199 | |
| 946 | 24 | | PK | 2-9 | 23-25-15 | D02647A | B11 | | | D02701 | 45 | | | 156-157, 166-199 | |
| 947 | 24 | | PK | 2-9 | 23-25-15 | D02647A | H11 | | | D02701 | 46 | | | 156-157, 166-199 | |
| 948 | 24 | | PK | 2-9 | 23-25-15 | D02647A | G13 | | | D02701 | 47 | | | 156-157, 166-199 | |
| 949 | 24 | | PK | 2-9 | 23-25-15 | D02647A | J13 | | | D02701 | 48 | | | 156-157, 166-199 | |
| 950 | 22 | | PA | 2-4 | 23-25-14 | D02647B | C11 | | | D06149P | 7 | | | 156-157, 166-199 | |
| 951 | 22 | | PA | 2-4 | 23-25-14 | D02647B | D11 | | | D06155P | 9 | | | 156-157, 166-199 | |
| FRB | | | | 0-0 | 23-25-13 | D96101P | | | HW | D96101P | 29 | | | 156-157, 166-199 | |
| W0095 | 286T0095 | | | SATCOM SYSTEM ,E9-1 SHELF,R | | | | | | | | | | | |
| 001 | 24 | | PV AA | 3-0 | 23-25-14 | D06155P | 19 | | | TB0257F | C021 | 2 | | 156-157, 166-199, 277-299 | |
| 001Z | | | AA | 0-0 | 23-25-14 | D06155P | 18 | | | TB0257F | A021 | 2 | | 156-157, 166-199, 277-299 | |
| 002 | 24 | | PV AB | 3-0 | 23-25-14 | D06155P | 21 | | | TB0257F | C023 | 2 | | 156-157, 166-199, 277-299 | |
| 002Z | | | AB | 0-0 | 23-25-14 | D06155P | 20 | | | TB0257F | A023 | 2 | | 156-157, 166-199, 277-299 | |
| 003 | 24 | | PK | 3-0 | 23-25-14 | D06155P | 22 | | | TB0257F | A025 | 2 | | 156-157, 166-199, 277-299 | |
| 004 | 24 | | PK | 3-0 | 23-25-14 | D06155P | 23 | | | TB0257F | C025 | 2 | | 156-157, 166-199, 277-299 | |
| 201B | 24 | | PW IA | 3-0 | 23-25-11 | D06155P | 3 | | | TB0257H | 7 | 2 | | 156-157, 166, 277-299 | |
| 201B | 24 | | PW IA | 3-0 | 23-25-11 | D06155P | 3 | | | TB0257H | 7 | # | | 167-199 | |
| 201R | 24 | | PW IA | 0-0 | 23-25-11 | D06155P | 2 | | | TB0257H | 5 | 2 | | 156-157, 166, 277-299 | |
| 201R | 24 | | PW IA | 0-0 | 23-25-11 | D06155P | 2 | | | TB0257H | 5 | # | | 167-199 | |
| 201Z | | | IA | 0-0 | 23-25-11 | D06155P | 1 | | | GDX0001 | S.. | 2 | | 156-157, 166-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W0090

Page 12

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------|--|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0095 | 286T0095 | | | | SATCOM SYSTEM ,E9-1 SHELF,R (continued) | | | | | | | | | | | |
| 205B | 24 | PW | IE | 3-0 | 23-25-13 | D06155P | 5 | | | | TB0257G | 12 | 2 | | 156-157, 166-199, 277-299 | |
| 205R | 24 | PW | IE | 0-0 | 23-25-13 | D06155P | 4 | | | | TB0257G | 11 | 2 | | 156-157, 166-199, 277-299 | |
| 205Z | | | IE | 0-0 | 23-25-13 | D06155P | 24 | | | | GDX0002 | S.. | 2 | | 156-157, 166-199, 277-299 | |
| 206B | 24 | PW | IF | 3-0 | 23-25-13 | D06155P | 14 | | | | TB0257F | C015 | 2 | | 156-157, 166-199, 277-299 | |
| 206R | 24 | PW | IF | 0-0 | 23-25-13 | D06155P | 13 | | | | TB0257F | A015 | 2 | | 156-157, 166-199, 277-299 | |
| 206Z | | | IF | 0-0 | 23-25-13 | D06155P | 12 | | | | GDX0002 | S.. | 2 | | 156-157, 166-199, 277-299 | |
| 207B | 24 | PW | IG | 3-0 | 23-25-13 | D06155P | 17 | | | | TB0257F | C019 | 2 | | 156-157, 166-199, 277-299 | |
| 207R | 24 | PW | IG | 0-0 | 23-25-13 | D06155P | 16 | | | | TB0257F | A019 | 2 | | 156-157, 166-199, 277-299 | |
| 207Z | | | IG | 0-0 | 23-25-13 | D06155P | 15 | | | | GDX0002 | S.. | 2 | | 156-157, 166-199, 277-299 | |
| W0098 | 286T0098 | | | | SHELF E2-4 INTEGRATION BUNDLE | | | | | | | | | | | |
| 002 | 24 | PK | | 4-1 | 29-11-32 | TB0176F | A021 | 2 | | | D05196P | 36 | | | ALL | |
| 003 | 22 | PA | | 4-3 | 28-21-11 | D05842P | 7 | | | | D02706B | H04 | | | ALL | |
| 004 | 22 | PA | | 4-3 | 28-21-11 | D05842P | 8 | | | | D02706B | A04 | | | ALL | |
| 005 | 22 | PA | | 4-3 | 28-21-11 | D05842P | 9 | | | | D02706B | H09 | | | ALL | |
| 006 | 22 | PA | | 4-4 | 28-21-11 | D05842P | 10 | | | | D02706A | H09 | | | ALL | |
| 007 | 22 | PA | | 4-4 | 28-21-11 | D05842P | 11 | | | | D02706A | A04 | | | ALL | |
| 008 | 22 | PA | | 4-4 | 28-21-11 | D05842P | 12 | | | | D02706A | H04 | | | ALL | |
| 009 | 24 | PK | | 6-0 | 31-51-21 | D04944P | 5 | | | | TB0176F | A070 | 2 | | 150-154, 275 | |
| 011 | 22 | PA | | 4-3 | 28-21-11 | D05196P | 27 | | | | D02706A | H06 | | | ALL | |
| 012 | 22 | PA | | 4-3 | 28-21-11 | D05196P | 28 | | | | D02706A | G08 | | | ALL | |
| 013 | 22 | PA | | 4-3 | 28-21-11 | D05196P | 29 | | | | D02706A | H07 | | | ALL | |
| 014 | 22 | PA | | 4-3 | 28-21-11 | D05196P | 30 | | | | D02706A | C06 | | | ALL | |
| 015 | 24 | PK | | 4-1 | 28-41-11 | D04944P | 7 | | | | D02706B | H06 | | | ALL | |
| 016 | 24 | PK | | 4-1 | 28-41-11 | D04944P | 14 | | | | D02706B | J04 | | | ALL | |
| 017 | 24 | PK | | 4-1 | 28-41-11 | D04944P | 21 | | | | D02706B | G11 | | | ALL | |
| 018 | 24 | PK | | 4-2 | 28-41-11 | D04944P | 28 | | | | D02706A | J04 | | | ALL | |
| 019 | 24 | PK | | 3-10 | 28-41-11 | TB0176F | A009 | 2 | | | D02706A | C14 | | | ALL | |
| 022 | 24 | PK | | 3-1 | 28-41-21 | D02706A | C01 | | | | D04448P | 1 | | | ALL | |
| 023 | 24 | PK | | 3-1 | 28-41-21 | D02706A | E01 | | | | D04448P | 2 | | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W0090
Page 13
Jan 21/2005



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0098 | 286T0098 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 024 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | E04 | | | D04448P | | 3 | | ALL |
| 025 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | D01 | | | D04448P | | 4 | | ALL |
| 026 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | C02 | | | D04448P | | 5 | | ALL |
| 027 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | E02 | | | D04448P | | 6 | | ALL |
| 028 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | F01 | | | D04448P | | 7 | | ALL |
| 029 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | D02 | | | D04448P | | 8 | | ALL |
| 030 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | C03 | | | D04448P | | 9 | | ALL |
| 031 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | E03 | | | D04448P | | 10 | | ALL |
| 032 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | F02 | | | D04448P | | 11 | | ALL |
| 033 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | D03 | | | D04448P | | 12 | | ALL |
| 034 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | F03 | | | D04448P | | 13 | | ALL |
| 035 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | C04 | | | D04448P | | 14 | | ALL |
| 036 | 24 | | PK | | 3-1 | 28-41-21 | D02706A | | D04 | | | D04448P | | 15 | | ALL |
| 037 | 24 | | PV | AB | 4-6 | 28-41-22 | D02706C | | 2 | GR | | D04638P | | 1 | | ALL |
| 037Z | | | | AB | 0-0 | 28-41-22 | D02706C | | =2 | | | D04638P | | =C1 | | ALL |
| 038 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | C01 | | | D04804P | | 5 | | ALL |
| 039 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | E01 | | | D04804P | | 6 | | ALL |
| 040 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | E04 | | | D04804P | | 7 | | ALL |
| 041 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | D01 | | | D04804P | | 28 | | ALL |
| 042 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | C02 | | | D04804P | | 29 | | ALL |
| 043 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | E02 | | | D04804P | | 10 | | ALL |
| 044 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | F01 | | | D04804P | | 11 | | ALL |
| 045 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | D02 | | | D04804P | | 12 | | ALL |
| 046 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | C03 | | | D04804P | | 13 | | ALL |
| 047 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | E03 | | | D04804P | | 14 | | ALL |
| 048 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | F02 | | | D04804P | | 15 | | ALL |
| 049 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | D03 | | | D04804P | | 16 | | ALL |
| 050 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | F03 | | | D04804P | | 17 | | ALL |
| 051 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | C04 | | | D04804P | | 18 | | ALL |
| 052 | 24 | | PK | | 4-7 | 28-41-22 | D02706B | | D04 | | | D04804P | | 19 | | ALL |
| 053 | 24 | | PV | AC | 2-11 | 28-41-21 | D02706C | | 3 | GR | | D04466P | | 1 | | ALL |
| 053Z | | | | AC | 0-0 | 28-41-21 | D02706C | | =3 | | | D04466P | | =C1 | | ALL |
| 054 | 20 | | PA | | 2-9 | 28-41-12 | D02706C | | 6 | | | GDX0002 | | D.. | 2 | ALL |
| 055 | 22 | | PQ | BT | 4-6 | 28-41-12 | D02706C | | 4 | | | D04804P | | 9 | | ALL |
| 055Z | | | | BT | 0-0 | 28-41-12 | D02706C | | DED | | | D04804P | | DED | | ALL |
| 056 | 22 | | PA | | 4-1 | 28-41-12 | D02706C | | 1 | | | D05196P | | 40 | | ALL |
| 057 | 20 | | PA | | 2-9 | 28-41-12 | D02706C | | 5 | | | GDX0002 | | D.. | 2 | ALL |
| 058 | 24 | | PV | AD | 4-6 | 28-41-23 | D02706C | | 7 | GR | | D05878P | | 1 | | ALL |
| 058Z | | | | AD | 0-0 | 28-41-23 | D02706C | | =7 | | | D05878P | | =C1 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0090

Page 14

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0098 | 286T0098 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 059 | 24 | | PK | | 4-7 | 28-41-23 | D02706B | E11 | | | D04804P | 30 | | | ALL |
| 060 | 22 | | PQ | AA | 7-0 | 27-51-61 | D05676P | 7 | | | M02187 | B | D | | ALL |
| 060Z | | | | AA | 0-0 | 27-51-61 | D05676P | DED | | | M02187 | DED | | | ALL |
| 061 | 24 | | PK | | 4-7 | 28-41-23 | D02706B | F10 | | | D04804P | 32 | | | ALL |
| 062 | 24 | | PK | | 4-7 | 28-41-23 | D02706B | D10 | | | D04804P | 33 | | | ALL |
| 063 | 24 | | PK | | 4-7 | 28-41-23 | D02706B | E10 | | | D04804P | 34 | | | ALL |
| 064 | 24 | | PK | | 4-7 | 28-41-23 | D02706B | D11 | | | D04804P | 35 | | | ALL |
| 065 | 24 | | PV | AG | 4-0 | 28-41-23 | D02706C | 8 | GR | | D04320P | 1 | | | ALL |
| 065Z | | | | AG | 0-0 | 28-41-23 | D02706C | = 8 | | | D04320P | = C1 | | | ALL |
| 066 | 24 | | PK | | 4-3 | 28-41-23 | D02706A | D10 | | | D05196P | 41 | | | ALL |
| 067 | 24 | | PK | | 4-3 | 28-41-23 | D02706A | E10 | | | D05196P | 37 | | | ALL |
| 068 | 24 | | PK | | 4-3 | 28-41-23 | D02706A | D11 | | | D05196P | 38 | | | ALL |
| 069 | 24 | | PK | | 4-3 | 28-41-23 | D02706A | E11 | | | D05196P | 39 | | | ALL |
| 070 | 24 | | PK | | 4-2 | 28-41-23 | D02706B | F11 | | | D05196P | 42 | | | ALL |
| 071 | 20 | | PQ | AR | 3-6 | 24-11-21 | D05676P | 2 | | | TB0176F | A084 | 2 | | ALL |
| 071Z | | | | AR | 0-0 | 24-11-21 | D05676P | DED | | | TB0176F | DED | | | ALL |
| 072 | 18 | | PQ | AS | 5-4 | 24-11-21 | D05676P | 1 | DK | | TB0176G | 23 | 2 | | ALL |
| 072Z | | | | AS | 0-0 | 24-11-21 | D05676P | DED | | | TB0176G | DED | | | ALL |
| 075 | 22 | | PA | | 6-2 | 33-16-22 | D05676P | 9 | | | TB0176F | A110 | 2 | | ALL |
| 080 | 24 | | PK | | 4-0 | 31-51-21 | D04944P | 4 | | | TB0176F | C021 | 2 | | 150-154, 275 |
| 081 | 24 | | PK | | 4-3 | 28-41-11 | D05196P | 21 | | | D02706A | C07 | | | ALL |
| 082 | 24 | | PK | | 4-3 | 28-41-11 | D05196P | 23 | | | D02706A | D08 | | | ALL |
| 083 | 20 | | PA | | 2-10 | 28-41-12 | D02706C | 11 | | | GDX0001 | S.. | 2 | | ALL |
| 084 | 24 | | PK | | 3-9 | 31-51-21 | D05842P | 5 | | | TB0176F | A012 | 2 | | 150-154, 275 |
| 085 | 24 | | PK | | 3-9 | 31-51-21 | D05842P | 6 | | | TB0176F | C012 | 2 | | 150-154, 275 |
| 086 | 24 | | PK | | 0-7 | 28-41-11 | D02706B | E09 | | | D02706B | C09 | | | ALL |
| 087 | 24 | | PK | | 0-7 | 28-41-11 | D02706A | E09 | | | D02706A | C09 | | | ALL |
| 091 | 20 | | UA | | 1-6 | 34-61-14 | D02706A | | | FC | GDX0005 | S.. | 2 | | 050-099 |
| 091 | 20 | | UA | | 2-8 | 34-61-14 | D02706A | | | FC | GDX0003 | S.. | 2 | | 150-199, 275-299 |
| 092 | 20 | | UA | | 1-6 | 34-61-24 | D02706B | | | FD | GDX0005 | S.. | 2 | | 050-099 |
| 092 | 20 | | UA | | 2-7 | 34-61-24 | D02706B | | | FD | GDX0003 | S.. | 2 | | 150-199, 275-299 |
| 093 | 20 | | PA | | 2-9 | 28-21-11 | D02706C | 9 | | | GDX0008 | D.. | 2 | | ALL |
| 094 | 20 | | PA | | 2-9 | 28-21-11 | D02706C | 10 | | | GDX0008 | D.. | 2 | | ALL |
| 095 | 22 | | PA | | 3-0 | 28-41-11 | D02706A | H11 | | | GDX0008 | A.. | 2 | | ALL |
| 096 | 24 | | PV | AJ | 3-9 | 27-51-61 | D05676P | 8 | | | TB0176F | C073 | 2 | | ALL |
| 096Z | | | | AJ | 0-0 | 27-51-61 | D05676P | DED | | | TB0176F | DED | | | ALL |
| 097 | 24 | | PK | | 3-3 | 28-41-13 | D02706A | H14 | | | TB0176F | A146 | 2 | | ALL |
| 098 | 22 | | PA | | 3-3 | 28-41-13 | D02706A | J08 | | | TB0176F | C146 | 2 | | ALL |
| 099 | 24 | | PK | | 5-4 | 31-31-26 | D05676P | 3 | | | TB0176F | A027 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0090

Page 15

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|----------|---------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0098 | 286T0098 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 108 | 22 | PQ | CC | 4-1 | 27-51-61 | M02187 | | A | D | | TB0176F | C064 | 2 | | 050-099 |
| 108 | 22 | PQ | CC | 5-2 | 27-51-61 | M02187 | | A | D | | TB0176F | C064 | 2 | | 150-199, 275-299 |
| 108Z | | | CC | 0-0 | 27-51-61 | TB0176F | | DED | | | M02187 | DED | | | 050-099 |
| 108Z | | | CC | 0-0 | 27-51-61 | M02187 | | DED | | | TB0176F | DED | | | 150-199, 275-299 |
| 167 | 20 | PQ | BG | 4-5 | 25-31-11 | D04804P | | 22 | | | TB0176F | A051 | 2 | | 275-276 |
| 167Z | | | BG | 0-0 | 25-31-11 | D04804P | | DED | | | TB0176F | DED | | | 275-276 |
| 169 | 24 | PV | BD | 5-0 | 24-22-22 | D04804P | | 31 | | | TB0176F | A032 | 2 | | ALL |
| 169Z | | | BD | 0-0 | 24-22-22 | D04804P | | DED | | | TB0176F | DED | | | ALL |
| 201B | 24 | PL | D | 4-1 | 28-41-11 | D02706B | | F06 | | | D04944P | 8 | | | ALL |
| 201R | 24 | PL | D | 0-0 | 28-41-11 | D02706B | | G06 | | | D04944P | 9 | | | ALL |
| 202B | 24 | PL | E | 4-1 | 28-41-11 | D02706B | | F08 | | | D04944P | 10 | | | ALL |
| 202R | 24 | PL | E | 0-0 | 28-41-11 | D02706B | | G08 | | | D04944P | 11 | | | ALL |
| 203B | 24 | PL | F | 4-1 | 28-41-11 | D02706B | | F07 | | | D04944P | 12 | | | ALL |
| 203R | 24 | PL | F | 0-0 | 28-41-11 | D02706B | | G07 | | | D04944P | 13 | | | ALL |
| 204B | 24 | PL | G | 4-1 | 28-41-11 | D02706B | | J01 | | | D04944P | 15 | | | ALL |
| 204R | 24 | PL | G | 0-0 | 28-41-11 | D02706B | | K01 | | | D04944P | 16 | | | ALL |
| 205B | 24 | PL | H | 4-1 | 28-41-11 | D02706B | | J03 | | | D04944P | 17 | | | ALL |
| 205R | 24 | PL | H | 0-0 | 28-41-11 | D02706B | | K03 | | | D04944P | 18 | | | ALL |
| 206B | 24 | PL | I | 4-1 | 28-41-11 | D02706B | | J02 | | | D04944P | 19 | | | ALL |
| 206R | 24 | PL | I | 0-0 | 28-41-11 | D02706B | | K02 | | | D04944P | 20 | | | ALL |
| 207B | 24 | PL | J | 4-1 | 28-41-11 | D02706B | | H10 | | | D04944P | 22 | | | ALL |
| 207R | 24 | PL | J | 0-0 | 28-41-11 | D02706B | | H11 | | | D04944P | 23 | | | ALL |
| 208B | 24 | PL | K | 4-1 | 28-41-11 | D02706B | | K10 | | | D04944P | 24 | | | ALL |
| 208R | 24 | PL | K | 0-0 | 28-41-11 | D02706B | | K11 | | | D04944P | 25 | | | ALL |
| 209B | 24 | PL | L | 4-1 | 28-41-11 | D02706B | | J10 | | | D04944P | 26 | | | ALL |
| 209R | 24 | PL | L | 0-0 | 28-41-11 | D02706B | | J11 | | | D04944P | 27 | | | ALL |
| 210B | 24 | PL | M | 4-2 | 28-41-11 | D02706A | | J01 | | | D04944P | 29 | | | ALL |
| 210R | 24 | PL | M | 0-0 | 28-41-11 | D02706A | | K01 | | | D04944P | 30 | | | ALL |
| 211B | 24 | PL | N | 4-2 | 28-41-11 | D02706A | | J03 | | | D04944P | 31 | | | ALL |
| 211R | 24 | PL | N | 0-0 | 28-41-11 | D02706A | | K03 | | | D04944P | 32 | | | ALL |
| 212B | 24 | PL | O | 4-2 | 28-41-11 | D02706A | | J02 | | | D04944P | 33 | | | ALL |
| 212R | 24 | PL | O | 0-0 | 28-41-11 | D02706A | | K02 | | | D04944P | 34 | | | ALL |
| 213B | 24 | PL | P | 4-1 | 28-41-11 | D02706B | | C07 | | | D04944P | 35 | | | ALL |
| 213R | 24 | PL | P | 0-0 | 28-41-11 | D02706B | | E07 | | | D04944P | 36 | | | ALL |
| 214B | 24 | PL | Q | 4-2 | 28-41-11 | D02706B | | A01 | | | D05196P | 2 | | | ALL |
| 214R | 24 | PL | Q | 0-0 | 28-41-11 | D02706B | | K09 | | | D05196P | 8 | | | ALL |
| 215B | 24 | PL | R | 4-2 | 28-41-11 | D02706B | | A03 | | | D05196P | 4 | | | ALL |
| 215R | 24 | PL | R | 0-0 | 28-41-11 | D02706B | | B03 | | | D05196P | 5 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0090

Page 16

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0098 | 286T0098 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 216B | 24 | PL | BA | 4-3 | 28-41-11 | D05196P | 25 | | | D02706A | A07 | | | 050-099, 150-156, 162-166, 275-276 | |
| 216B | 24 | PL | BA | 4-3 | 28-41-11 | D02706A | A07 | | | D05196P | 25 | | | 157, 167-199, 277-299 | |
| 216R | 24 | PL | BA | 0-0 | 28-41-11 | D05196P | 24 | | | D02706A | K07 | | | 050-099, 150-156, 162-166, 275-276 | |
| 216R | 24 | PL | BA | 0-0 | 28-41-11 | D02706A | K07 | | | D05196P | 24 | | | 157, 167-199, 277-299 | |
| 217B | 24 | PL | BB | 4-1 | 28-41-11 | D02706B | A07 | | | D04944P | 2 | | | ALL | |
| 217R | 24 | PL | BB | 0-0 | 28-41-11 | D02706B | K07 | | | D04944P | 3 | | | ALL | |
| 218B | 24 | PL | U | 4-3 | 28-41-11 | D02706A | C10 | | | D05196P | 10 | | | ALL | |
| 218R | 24 | PL | U | 0-0 | 28-41-11 | D02706A | C11 | | | D05196P | 11 | | | ALL | |
| 220B | 24 | PL | W | 4-3 | 28-41-11 | D02706A | A01 | | | D05196P | 14 | | | ALL | |
| 220R | 24 | PL | W | 0-0 | 28-41-11 | D02706A | K09 | | | D05196P | 15 | | | ALL | |
| 221B | 24 | PL | X | 4-3 | 28-41-11 | D02706A | A03 | | | D05196P | 17 | | | ALL | |
| 221R | 24 | PL | X | 0-0 | 28-41-11 | D02706A | B03 | | | D05196P | 18 | | | ALL | |
| 224B | 24 | PL | B | 3-1 | 28-41-21 | D02706A | G01 | | | D04448P | 16 | | | ALL | |
| 224R | 24 | PL | B | 0-0 | 28-41-21 | D02706A | H01 | | | D04448P | 17 | | | ALL | |
| 225B | 24 | PL | C | 3-1 | 28-41-21 | D02706A | G02 | | | D04448P | 18 | | | ALL | |
| 225R | 24 | PL | C | 0-0 | 28-41-21 | D02706A | H02 | | | D04448P | 19 | | | ALL | |
| 226B | 24 | PL | Z | 4-7 | 28-41-22 | D02706B | G02 | | | D04804P | 1 | | | ALL | |
| 226R | 24 | PL | Z | 0-0 | 28-41-22 | D02706B | H02 | | | D04804P | 2 | | | ALL | |
| 228B | 24 | PL | AE | 4-7 | 28-41-23 | D02706B | B10 | | | D04804P | 20 | | | ALL | |
| 228R | 24 | PL | AE | 0-0 | 28-41-23 | D02706B | B11 | | | D04804P | 21 | | | ALL | |
| 232B | 24 | PL | AL | 4-7 | 28-41-22 | D02706B | G01 | | | D04804P | 24 | | | ALL | |
| 232R | 24 | PL | AL | 0-0 | 28-41-22 | D02706B | H01 | | | D04804P | 25 | | | ALL | |
| 233B | 24 | PL | AM | 4-7 | 28-41-23 | D02706B | A10 | | | D04804P | 36 | | | ALL | |
| 233R | 24 | PL | AM | 0-0 | 28-41-23 | D02706B | A11 | | | D04804P | 37 | | | ALL | |
| 234B | 24 | PW | AH | 3-10 | 28-41-11 | D02706B | B08 | | | TB0176G | 166 | 2 | | ALL | |
| 234R | 24 | PW | AH | 0-0 | 28-41-11 | D02706B | A08 | | | TB0176G | 165 | 2 | | ALL | |
| 234Z | | | AH | 0-0 | 28-41-11 | D02706B | DED | | | GDY0010 | S.. | 2 | | 050-099, 162-199, 277-299 | |
| 234Z | | | AH | 0-0 | 28-41-11 | D02706B | DED | | | GDY0011 | S.. | 2 | | 150-157, 275-276 | |
| 235B | 24 | PW | AO | 3-4 | 34-61-14 | D02706A | K11 | | | TB0176F | C127 | 2 | | ALL | |
| 235R | 24 | PW | AO | 0-0 | 34-61-14 | D02706A | J11 | | | TB0176F | A127 | 2 | | ALL | |
| 235Z | | | AO | 0-0 | 34-61-14 | D02706A | | | FC | TB0176F | A026 | 2 | | ALL | |
| 236B | 24 | PW | AP | 3-3 | 34-61-24 | D02706B | B06 | | | TB0176F | C128 | 2 | | ALL | |
| 236R | 24 | PW | AP | 0-0 | 34-61-24 | D02706B | A06 | | | TB0176F | A128 | 2 | | ALL | |
| 236Z | | | AP | 0-0 | 34-61-24 | D02706B | | | FD | TB0176F | C028 | 2 | | ALL | |
| 237B | 24 | PL | BC | 3-3 | 28-41-13 | D02706A | K14 | | | TB0176F | C147 | 2 | | ALL | |
| 237R | 24 | PL | BC | 0-0 | 28-41-13 | D02706A | A14 | | | TB0176F | A147 | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W0090
Page 17
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0098 | 286T0098 | | | SHELF E2-4 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 301B | 24 | PM | S | 4-2 | 28-41-11 | D02706B | A02 | | | D05196P | 6 | | | ALL | |
| 301R | 24 | PM | S | 0-0 | 28-41-11 | D02706B | B02 | | | D05196P | 7 | | | ALL | |
| 301Y | 24 | PM | S | 0-0 | 28-41-11 | D02706B | B01 | | | D05196P | 3 | | | ALL | |
| 302B | 24 | PM | T | 4-3 | 28-41-11 | D02706A | B10 | | | D05196P | 12 | | | ALL | |
| 302R | 24 | PM | T | 0-0 | 28-41-11 | D02706A | B11 | | | D05196P | 13 | | | ALL | |
| 302Y | 24 | PM | T | 0-0 | 28-41-11 | D02706A | A11 | | | D05196P | 9 | | | ALL | |
| 303B | 24 | PM | V | 4-3 | 28-41-11 | D02706A | A02 | | | D05196P | 19 | | | ALL | |
| 303R | 24 | PM | V | 0-0 | 28-41-11 | D02706A | B02 | | | D05196P | 20 | | | ALL | |
| 303Y | 24 | PM | V | 0-0 | 28-41-11 | D02706A | B01 | | | D05196P | 16 | | | ALL | |
| 401B | 22 | PD | A | 4-3 | 28-21-11 | D05196P | 31 | | | D02706A | E06 | | | 050-099, 150-156, 162-166, 275-276 | |
| 401B | 22 | PD | A | 4-3 | 28-21-11 | D02706A | E06 | | | D05196P | 31 | | | 157, 167-199, 277-299 | |
| 401G | 22 | PD | A | 0-0 | 28-21-11 | D05196P | 32 | | | D02706A | F06 | | | 050-099, 150-156, 162-166, 275-276 | |
| 401G | 22 | PD | A | 0-0 | 28-21-11 | D02706A | F06 | | | D05196P | 32 | | | 157, 167-199, 277-299 | |
| 401R | 22 | PD | A | 0-0 | 28-21-11 | D05196P | 33 | | | D02706A | E07 | | | 050-099, 150-156, 162-166, 275-276 | |
| 401R | 22 | PD | A | 0-0 | 28-21-11 | D02706A | E07 | | | D05196P | 33 | | | 157, 167-199, 277-299 | |
| 401Y | 22 | PD | A | 0-0 | 28-21-11 | D05196P | 34 | | | D02706A | F07 | | | 050-099, 150-156, 162-166, 275-276 | |
| 401Y | 22 | PD | A | 0-0 | 28-21-11 | D02706A | F07 | | | D05196P | 34 | | | 157, 167-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W0090
Page 18 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|----------|---------|---------|-------|------|------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0100 | 286T0100 | | | AFT CABIN LWR CEILING CENTER (D) | | | | | | | | | | | |
| 001 | 22 | PA | | 4-0 | 33-22-42 | D02866 | | 8 | | | L00219 | =G | E | * | 050-099 |
| 001 | 22 | PA | | 4-0 | 33-27-11 | D12108 | | 8 | | | L01176 | =G | E | * | 275-299 |
| 004 | 22 | PA | | 4-0 | 33-22-42 | D02866 | | 11 | | | SM00001 | | 9 | | 050-099 |
| 004 | 22 | PA | | 4-0 | 33-27-11 | D12108 | | 11 | | | SM00001 | | 9 | | 275-299 |
| 005 | 22 | PA | | 4-0 | 33-22-42 | D02866 | | 12 | | | SM00002 | | 9 | | 050-099 |
| 005 | 22 | PA | | 4-0 | 33-27-11 | D12108 | | 12 | | | SM00002 | | 9 | | 275-299 |
| 006 | 22 | PA | | 4-0 | 33-22-42 | SM00001 | | | 9 | | L00219 | =4 | C | | 050-099 |
| 006 | 22 | PA | | 4-0 | 33-27-11 | SM00001 | | | 9 | | L01176 | =4 | C | | 275-299 |
| 007 | 22 | PA | | 4-0 | 33-22-42 | SM00002 | | | 9 | | L00219 | =3 | C | | 050-099 |
| 007 | 22 | PA | | 4-0 | 33-27-11 | SM00002 | | | 9 | | L01176 | =3 | C | | 275-299 |
| 008 | 22 | PA | | 5-0 | 33-22-42 | D06038P | | 6 | | | L00219 | =G | E | * | 050-099 |
| 008 | 22 | PA | | 5-0 | 33-27-11 | D06038P | | 6 | | | L01176 | =G | E | * | 275-299 |
| 009 | 22 | PA | | 4-0 | 33-22-42 | D02868 | | 8 | | | L00219 | =G | E | * | 050-099 |
| 009 | 22 | PA | | 4-0 | 33-27-11 | D12110 | | 8 | | | L01176 | =G | E | * | 275-299 |
| 012 | 22 | PA | | 4-0 | 33-22-42 | D02866 | | 10 | | | L00219 | =2 | C | | 050-099 |
| 012 | 22 | PA | | 4-0 | 33-27-11 | D12108 | | 10 | | | L01176 | =2 | C | | 275-299 |
| 013 | 22 | PA | | 4-0 | 33-22-42 | D02866 | | 9 | | | L00219 | =1 | C | | 050-099 |
| 013 | 22 | PA | | 4-0 | 33-27-11 | D12108 | | 9 | | | L01176 | =1 | C | | 275-299 |
| 016 | 22 | PA | | 4-0 | 33-22-42 | D02868 | | 11 | | | SP01214 | | 9 | | 050-099 |
| 016 | 22 | PA | | 4-0 | 33-27-11 | D12110 | | 11 | | | SP01214 | | 9 | | 275-299 |
| 017 | 22 | PA | | 4-0 | 33-22-42 | D02868 | | 12 | | | SP01216 | | 9 | | 050-099 |
| 017 | 22 | PA | | 4-0 | 33-27-11 | D12110 | | 12 | | | SP01216 | | 9 | | 275-299 |
| 027 | 22 | PA | | 5-0 | 33-22-42 | D02866 | | 5 | | | D06038P | 4 | | | 050-099 |
| 027 | 22 | PA | | 5-0 | 33-27-11 | D12108 | | 5 | | | D06038P | 4 | | | 275-299 |
| 028 | 22 | PA | | 4-0 | 33-22-42 | D02866 | | 2 | | | L00220 | =1 | C | | 050-099 |
| 028 | 22 | PA | | 4-0 | 33-27-11 | D12108 | | 2 | | | L01177 | =1 | C | | 275-299 |
| 029 | 22 | PA | | 4-0 | 33-22-42 | D02866 | | 3 | | | L00220 | =2 | C | | 050-099 |
| 029 | 22 | PA | | 4-0 | 33-27-11 | D12108 | | 3 | | | L01177 | =2 | C | | 275-299 |
| 030 | 22 | PA | | 5-0 | 33-22-42 | D02866 | | 7 | | | D06038P | 1 | | | 050-099 |
| 030 | 22 | PA | | 5-0 | 33-27-11 | D12108 | | 7 | | | D06038P | 1 | | | 275-299 |
| 031 | 22 | PA | | 5-0 | 33-22-42 | D02868 | | 5 | | | D06038P | 5 | | | 050-099 |
| 031 | 22 | PA | | 5-0 | 33-27-11 | D12110 | | 5 | | | D06038P | 5 | | | 275-299 |
| 032 | 22 | PA | | 5-0 | 33-22-42 | D02868 | | 7 | | | D06038P | 9 | | | 050-099 |
| 032 | 22 | PA | | 5-0 | 33-27-11 | D12110 | | 7 | | | D06038P | 9 | | | 275-299 |
| 033 | 22 | PA | | 4-0 | 33-22-42 | L00220 | | | =4 | C | SM00001 | | 9 | | 050-099 |
| 033 | 22 | PA | | 4-0 | 33-27-11 | SM00001 | | | 9 | | L01177 | =4 | C | | 275-299 |
| 034 | 22 | PA | | 4-0 | 33-22-42 | L00220 | | | =3 | C | SM00002 | | 9 | | 050-099 |
| 034 | 22 | PA | | 4-0 | 33-27-11 | SM00002 | | | 9 | | L01177 | =3 | C | | 275-299 |
| G-A | | | | 0-0 | 33-22-42 | L00221 | | | BLK | | D02868 | | 10 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 1

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0100 | 286T0100 | | | AFT CABIN LWR CEILING CENTER (D) (continued) | | | | | | | | | | | |
| G-A | | | | 0-0 | 33-27-11 | L01178 | | BLK | | D12110 | | 10 | | 275-299 | |
| G-B | | | | 0-0 | 33-22-42 | L00221 | | BLK | | D02868 | | 9 | | 050-099 | |
| G-B | | | | 0-0 | 33-27-11 | L01178 | | BLK | | D12110 | | 9 | | 275-299 | |
| G-C | | | | 0-0 | 33-22-42 | L00221 | | WHT | | SP01216 | | 9 | | 050-099 | |
| G-C | | | | 0-0 | 33-27-11 | L01178 | | WHT | | SP01216 | | 9 | | 275-299 | |
| G-D | | | | 0-0 | 33-22-42 | L00221 | | WHT | | SP01214 | | 9 | | 050-099 | |
| G-D | | | | 0-0 | 33-27-11 | L01178 | | WHT | | SP01214 | | 9 | | 275-299 | |
| H-A | | | | 0-0 | 33-22-42 | L00222 | | BLK | | D02868 | | 2 | | 050-099 | |
| H-A | | | | 0-0 | 33-27-11 | L01179 | | BLK | | D12110 | | 2 | | 275-299 | |
| H-B | | | | 0-0 | 33-22-42 | L00222 | | BLK | | D02868 | | 3 | | 050-099 | |
| H-B | | | | 0-0 | 33-27-11 | L01179 | | BLK | | D12110 | | 3 | | 275-299 | |
| H-C | | | | 0-0 | 33-22-42 | L00222 | | WHT | | SP01214 | | 9 | | 050-099 | |
| H-C | | | | 0-0 | 33-27-11 | L01179 | | WHT | | SP01214 | | 9 | | 275-299 | |
| H-D | | | | 0-0 | 33-22-42 | L00222 | | WHT | | SP01216 | | 9 | | 050-099 | |
| H-D | | | | 0-0 | 33-27-11 | L01179 | | WHT | | SP01216 | | 9 | | 275-299 | |
| W0101 | 286T0101 | | | E1-1 SHELF | | | | | | | | | | | |
| 001 | 22 | PA | | 3-1 | 27-11-12 | D05413J | | 10 | | D00665A | | E07 | | ALL | |
| 002 | 22 | PA | | 3-1 | 27-11-12 | D05413J | | 11 | | D00665A | | E08 | | ALL | |
| 003 | 22 | PA | | 3-3 | 27-21-12 | D05495J | | 5 | | TB0101G | | 6 | 2 | ALL | |
| 005 | 22 | PA | | 3-0 | 27-21-12 | D01263A | | D12 | | TB0101G | | 6 | 2 | ALL | |
| 007 | 22 | PA | | 4-7 | 27-21-12 | D05413J | | 12 | | TB0101G | | 6 | 2 | ALL | |
| 008 | 22 | PA | | 3-9 | 27-21-22 | D05413J | | 13 | | D01263A | | C06 | | ALL | |
| 010 | 22 | PA | | 3-8 | 27-21-22 | D05413J | | 22 | | D01263B | | A01 | | ALL | |
| 011 | 22 | PA | | 3-8 | 27-21-22 | D05413J | | 23 | | D01263B | | D01 | | ALL | |
| 012 | 22 | PA | | 3-8 | 27-21-22 | D05413J | | 24 | | D01263B | | B01 | | ALL | |
| 013 | 22 | PA | | 3-5 | 27-41-11 | D00665A | | B04 | | D01251A | | B05 | | ALL | |
| 014 | 22 | PA | | 3-5 | 27-41-11 | D00665A | | A04 | | D01251A | | E02 | | ALL | |
| 015 | 22 | PA | | 3-5 | 27-41-11 | D00665A | | B05 | | D01253A | | B05 | | ALL | |
| 016 | 22 | PA | | 3-5 | 27-41-11 | D00665A | | A05 | | D01253A | | E02 | | ALL | |
| 017 | 22 | PA | | 3-9 | 27-41-11 | D04353J | | 2 | | TB0101G | | 102 | 2 | 150-154 | |
| 018 | 22 | PQ | AR | 3-7 | 27-41-31 | D00665A | | B06 | | TB0101G | | 102 | 2 | 050-099, 155-199, 275-299 | |
| 018 | 22 | PA | | 3-7 | 27-41-11 | D00665A | | B06 | | TB0101G | | 102 | 2 | 150-154 | |
| 018Z | | | AR | 0-0 | 27-41-31 | D00665A | | DED | | TB0101G | | DED | | 050-099, 155-199, 275-299 | |
| 025 | 22 | PA | | 2-11 | 22-21-11 | D01259A | | C02 | | D01253A | | G01 | | ALL | |
| 026 | 22 | PA | | 2-11 | 22-21-11 | D01259A | | A02 | | D01253A | | B08 | | ALL | |
| 033 | 22 | PA | | 0-7 | 27-61-15 | D00827B | | D06 | | D00827B | | D07 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 2

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0101 | 286T0101 | | | E1-1 SHELF (continued) | | | | | | | | | | | |
| 034 | 22 | | PA | | 0-7 | 27-61-15 | D00827B | | B06 | | D00827B | | B07 | | ALL |
| 037 | 22 | | PA | | 4-4 | 27-61-14 | D00825A | | F05 | | D01253A | | C07 | | ALL |
| 038 | 22 | | PA | | 4-4 | 27-61-14 | D00825A | | F03 | | D01253A | | H01 | | ALL |
| 039 | 22 | | PA | | 2-6 | 27-61-14 | D00825A | | G03 | | D01251A | | H01 | | ALL |
| 040 | 22 | | PA | | 2-6 | 27-61-14 | D00825A | | G05 | | D01251A | | C07 | | ALL |
| 044 | 22 | | PA | | 4-4 | 27-61-14 | D00825A | | E12 | | D01253A | | A05 | | ALL |
| 046 | 22 | | PA | | 0-7 | 27-61-14 | D00825A | | A08 | | D00825A | | C07 | | ALL |
| 049 | 22 | | PA | | 4-1 | 27-21-12 | D01263A | | D02 | | D01253A | | G03 | | ALL |
| 050 | 22 | | PA | | 4-1 | 27-21-12 | D01263A | | A02 | | D01253A | | A08 | | ALL |
| 051 | 22 | | PA | | 4-8 | 27-61-15 | D01253A | | A03 | | D01251A | | C03 | | ALL |
| 052 | 22 | | PA | | 4-6 | 27-61-15 | D01253A | | C01 | | TB0101H | 115 | 2 | | ALL |
| 054 | 22 | | PA | | 3-8 | 27-61-15 | D00827B | | F06 | | D01253A | | C08 | | ALL |
| 055 | 22 | | PA | | 3-8 | 27-61-15 | D00827B | | F04 | | D01253A | | H02 | | ALL |
| 057 | 22 | | PA | | 2-11 | 27-61-15 | D00827B | | G06 | | D01251A | | C08 | | ALL |
| 058 | 22 | | PA | | 2-11 | 27-61-15 | D00827B | | G04 | | D01251A | | H02 | | ALL |
| 061 | 22 | | PA | | 2-11 | 22-21-11 | D01259A | | B05 | | D01253A | | C05 | | ALL |
| 062 | 22 | | PA | | 2-11 | 22-21-11 | D01259A | | A05 | | D01253A | | E03 | | ALL |
| 065 | 22 | | PA | | 2-9 | 27-21-12 | D01263A | | D01 | | D01251A | | G03 | | ALL |
| 066 | 22 | | PA | | 2-9 | 27-21-12 | D01263A | | A01 | | D01251A | | A08 | | ALL |
| 070 | 22 | | PA | | 4-6 | 27-09-12 | D05413J | | 7 | | TB0101H | 103 | 2 | | ALL |
| 071 | 22 | | PA | | 3-9 | 27-09-12 | D04353J | | 9 | | TB0101H | 103 | 2 | | ALL |
| 072 | 22 | | PA | | 2-11 | 27-09-12 | D01263A | | D07 | | TB0101H | 103 | 2 | | ALL |
| 073 | 22 | | PA | | 4-1 | 27-09-12 | D01259A | | H04 | | TB0101H | 103 | 2 | | ALL |
| 074 | 22 | | PA | | 3-7 | 27-09-12 | D00665A | | D06 | | TB0101H | 103 | 2 | | ALL |
| 075 | 22 | | PA | | 4-5 | 27-09-12 | D00829B | | D10 | | TB0101H | 103 | 2 | | ALL |
| 076 | 22 | | PA | | 3-1 | 27-09-12 | D00827B | | D02 | | TB0101H | 103 | 2 | | ALL |
| 077 | 22 | | PA | | 2-8 | 27-09-12 | D00825A | | D01 | | TB0101H | 103 | 2 | | ALL |
| 078 | 22 | | PA | | 3-9 | 27-09-13 | D04353J | | 11 | | TB0101G | 106 | 2 | | ALL |
| 079 | 22 | | PA | | 3-9 | 27-09-13 | D04353J | | 10 | | TB0101G | 105 | 2 | | ALL |
| 080 | 22 | | PA | | 4-6 | 27-09-13 | D05413J | | 9 | | TB0101G | 106 | 2 | | ALL |
| 081 | 22 | | PA | | 4-6 | 27-09-13 | D05413J | | 8 | | TB0101G | 105 | 2 | | ALL |
| 082 | 22 | | PA | | 2-8 | 27-09-13 | D00825A | | K13 | | TB0101G | 106 | 2 | | ALL |
| 083 | 22 | | PA | | 2-8 | 27-09-13 | D00825A | | J13 | | TB0101G | 105 | 2 | | ALL |
| 086 | 22 | | PA | | 2-5 | 27-61-16 | D00829B | | F14 | | D01253A | | B07 | | ALL |
| 087 | 22 | | PA | | 2-5 | 27-61-16 | D00829B | | F12 | | D01253A | | H03 | | ALL |
| 091 | 22 | | PA | | 4-2 | 27-61-16 | D01251A | | B07 | | D00829B | | G14 | | ALL |
| 092 | 22 | | PA | | 4-2 | 27-61-16 | D01251A | | H03 | | D00829B | | G12 | | ALL |
| 096 | 22 | | PA | | 0-7 | 27-61-14 | D00825A | | D05 | | D00825A | | D06 | | ALL |
| 097 | 22 | | PA | | 0-7 | 27-61-14 | D00825A | | B05 | | D00825A | | B06 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0100
Page 3
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|-------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0101 | 286T0101 | | | E1-1 SHELF (continued) | | | | | | | | | | | |
| 101 | 22 | PA | | | 0-7 | 27-61-16 | D00829B | D14 | | | D00829B | D15 | | | ALL |
| 102 | 22 | PA | | | 0-7 | 27-61-16 | D00829B | B14 | | | D00829B | B15 | | | ALL |
| 110 | 22 | PA | | | 3-9 | 27-61-11 | D04353J | 13 | | | TB0101H | 108 | 2 | | ALL |
| 111 | 22 | PA | | | 4-6 | 27-61-11 | D05413J | 29 | | | TB0101H | 108 | 2 | | ALL |
| 112 | 22 | PA | | | 4-5 | 27-61-11 | D00829B | E10 | | | TB0101H | 108 | 2 | | ALL |
| 113 | 22 | PA | | | 3-1 | 27-61-11 | D00827B | E02 | | | TB0101H | 108 | 2 | | ALL |
| 114 | 22 | PA | | | 2-8 | 27-61-11 | D00825A | E01 | | | TB0101H | 108 | 2 | | ALL |
| 121 | 22 | PA | | | 3-10 | 22-21-11 | TB0101G | 3 | 2 | | D04353J | 24 | | | ALL |
| 122 | 22 | PA | | | 3-3 | 22-21-11 | D01259A | D04 | | | GDX0001 | D.. | 2 | | 050-099 |
| 123 | 22 | PA | | | 3-3 | 22-21-11 | D01259A | C04 | | | GDX0001 | D.. | 2 | | ALL |
| 124 | 22 | PA | | | 3-3 | 22-21-11 | D01259A | B04 | | | GDX0001 | D.. | 2 | | ALL |
| 128 | 22 | PA | | | 3-10 | 22-21-11 | D01259A | C01 | | | D01251A | G01 | | | ALL |
| 129 | 22 | PA | | | 3-10 | 22-21-11 | D01259A | A01 | | | D01251A | B08 | | | ALL |
| 131 | 22 | PA | | | 3-10 | 22-21-11 | D01259A | G05 | | | D01251A | C05 | | | ALL |
| 132 | 22 | PA | | | 3-10 | 22-21-11 | D01259A | G04 | | | D01251A | E03 | | | ALL |
| 133 | 22 | PA | | | 4-6 | 22-24-11 | D05413J | 3 | | | TB0101G | 101 | 2 | | ALL |
| 134 | 22 | PA | | | 3-7 | 22-24-11 | D00665A | A06 | | | TB0101G | 101 | 2 | | ALL |
| 135 | 22 | PA | | | 3-9 | 22-24-11 | D04353J | 8 | | | TB0101G | 101 | 2 | | ALL |
| 136 | 22 | PA | | | 2-1 | 22-21-11 | D04353J | 34 | | | D01259B | H10 | | | ALL |
| 140 | 22 | PA | | | 3-1 | 22-24-11 | D00665A | F11 | | | D05413J | 5 | | | ALL |
| 141 | 22 | PA | | | 3-1 | 22-24-11 | D00665A | E11 | | | D05413J | 6 | | | ALL |
| 143 | 22 | PA | | | 3-3 | 22-21-11 | D01259A | F04 | | | GDX0001 | D.. | 2 | | ALL |
| 144 | 22 | PA | | | 4-2 | 22-21-11 | D01259A | H05 | | | TB0101G | 3 | 2 | | ALL |
| 145 | 22 | PA | | | 4-7 | 22-21-11 | TB0101G | 3 | 2 | | D05413J | 1 | | | ALL |
| 146 | 22 | PA | | | 4-6 | 27-41-11 | D05413J | 4 | | | TB0101G | 102 | 2 | | 150-154 |
| 149 | 22 | PA | | | 3-7 | 27-41-11 | D00665A | D04 | | | TB0101G | 107 | 2 | | ALL |
| 150 | 22 | PQ | FY | | 2-10 | 27-41-11 | D05495J | 3 | | | TB0101H | 117 | 2 | | ALL |
| 150Z | | | FY | | 0-0 | 27-41-11 | D05495J | DED | | | TB0101H | DED | | | ALL |
| 151 | 22 | PQ | GA | | 3-3 | 27-41-11 | D00665A | F07 | | | TB0101H | 117 | 2 | | ALL |
| 151Z | | | GA | | 0-0 | 27-41-11 | D00665A | DED | | | TB0101H | DED | | | ALL |
| 152 | 22 | PQ | GB | | 3-3 | 27-41-11 | D00665A | F08 | | | TB0101H | 117 | 2 | | ALL |
| 152Z | | | GB | | 0-0 | 27-41-11 | D00665A | DED | | | TB0101H | DED | | | ALL |
| 153 | 22 | PA | | | 2-10 | 27-41-11 | D00665A | F09 | | | D05131J | 13 | | | ALL |
| 154 | 22 | PA | | | 2-10 | 27-41-11 | D00665A | F10 | | | D05131J | 14 | | | ALL |
| 156 | 22 | PA | | | 4-6 | 27-41-11 | D05413J | 25 | | | TB0101G | 107 | 2 | | ALL |
| 157 | 22 | PA | | | 4-7 | 27-41-11 | D05413J | 26 | | | TB0101G | 8 | 2 | | ALL |
| 165 | 22 | PA | | | 3-8 | 27-41-11 | D00665A | D05 | | | TB0101G | 8 | 2 | | ALL |
| 166 | 22 | PQ | GP | | 3-11 | 27-41-11 | D05131J | 12 | | | TB0101H | 117 | 2 | | ALL |
| 166Z | | | GP | | 0-0 | 27-41-11 | D05131J | DED | | | TB0101H | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 4

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------------------------|-------|-------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0101 | 286T0101 | E1-1 SHELF (continued) | | | | | | | | | | | | | |
| 167 | 22 | PA | | 4-5 | 27-41-11 | D05131J | | 10 | | | TB0101G | 8 | 2 | | ALL |
| 168 | 22 | PA | | 4-4 | 27-41-11 | D05131J | | 11 | | | TB0101G | 107 | 2 | | ALL |
| 169 | 22 | PA | | 3-1 | 27-41-11 | D00665A | | F12 | | | D05413J | 27 | | | ALL |
| 170 | 22 | PA | | 3-5 | 27-41-11 | D00665A | | C05 | | | D01251A | A07 | | | ALL |
| 172 | 22 | PA | | 3-5 | 27-41-11 | D00665A | | E04 | | | D01253A | G02 | | | ALL |
| 173 | 22 | PA | | 3-5 | 27-41-11 | D00665A | | E05 | | | D01253A | A07 | | | ALL |
| 175 | 22 | PA | | 3-5 | 27-41-11 | D00665A | | C04 | | | D01251A | G02 | | | ALL |
| 176 | 22 | PA | | 3-1 | 22-22-11 | D00665A | | G12 | | | D05413J | 2 | | | ALL |
| 177 | 22 | PA | | 3-1 | 27-41-11 | D00665A | | E12 | | | D05413J | 28 | | | ALL |
| 180 | 22 | PA | | 0-7 | 27-61-16 | D00829B | | D11 | | | D00829B | C11 | | | ALL |
| 181 | 22 | PA | | 2-6 | 27-61-16 | D00829B | | H12 | | | D04353J | 32 | | | ALL |
| 182 | 20 | PA | | 1-7 | 27-61-16 | GDX0007 | | D.. | 2 | | D04353J | 33 | | | ALL |
| 183 | 22 | PA | | 2-11 | 27-61-16 | D00829B | | C10 | | | D00665A | A01 | | | ALL |
| 198 | 22 | PA | | 2-6 | 27-61-14 | D01251A | | A05 | | | D00825A | E11 | | | ALL |
| 201B | 22 | PB | IA | 3-9 | 27-21-22 | D05413J | | 35 | | | D01263A | A04 | | | ALL |
| 201R | 22 | PB | IA | 0-0 | 27-21-22 | D05413J | | 34 | | | D01263A | A05 | | | ALL |
| 205 | 20 | UA | | 0-18 | 22-22-11 | D04353J | | | | FK | GDX0007 | S.. | 2 | | ALL |
| 205B | 24 | PW | IE | 2-3 | 22-22-11 | D00665A | | D08 | | | D04353J | 26 | | | ALL |
| 205R | 24 | PW | IE | 0-0 | 22-22-11 | D00665A | | D07 | | | D04353J | 25 | | | ALL |
| 205Z | | | IE | 0-0 | 22-22-11 | D00665A | | DED | | | D04353J | | | FK | ALL |
| 206B | 22 | PB | IF | 3-9 | 27-61-14 | D00825A | | G08 | | | D05411J | 3 | | | ALL |
| 206R | 22 | PB | IF | 0-0 | 27-61-14 | D00825A | | G09 | | | D05411J | 1 | | | ALL |
| 207B | 22 | PB | IG | 3-9 | 27-61-14 | D00825A | | G11 | | | D05411J | 11 | | | ALL |
| 207R | 22 | PB | IG | 0-0 | 27-61-14 | D00825A | | G10 | | | D05411J | 10 | | | ALL |
| 208B | 22 | PB | IH | 2-9 | 27-61-14 | D00825A | | J11 | | | TB0101G | 13 | 2 | | ALL |
| 208R | 22 | PB | IH | 0-0 | 27-61-14 | D00825A | | K11 | | | TB0101G | 12 | 2 | | ALL |
| 209B | 22 | PB | II | 4-5 | 27-61-14 | D05411J | | 15 | | | TB0101G | 13 | 2 | | ALL |
| 209R | 22 | PB | II | 0-0 | 27-61-14 | D05411J | | 14 | | | TB0101G | 12 | 2 | | ALL |
| 210B | 22 | PB | IJ | 4-5 | 27-61-14 | D05411J | | 9 | | | TB0101G | 13 | 2 | | ALL |
| 210R | 22 | PB | IJ | 0-0 | 27-61-14 | D05411J | | 8 | | | TB0101G | 12 | 2 | | ALL |
| 211B | 22 | PB | IK | 2-4 | 27-61-14 | D00825A | | J06 | | | TB0101H | 115 | 2 | | ALL |
| 211R | 22 | PB | IK | 0-0 | 27-61-14 | D00825A | | K06 | | | TB0101H | 113 | 2 | | ALL |
| 212B | 22 | PB | IL | 3-11 | 27-61-15 | D05131J | | 9 | | | TB0101H | 115 | 2 | | ALL |
| 212R | 22 | PB | IL | 0-0 | 27-61-15 | D05131J | | 8 | | | TB0101H | 113 | 2 | | ALL |
| 213B | 22 | PB | IM | 3-11 | 27-61-15 | D05131J | | 2 | | | TB0101H | 115 | 2 | | ALL |
| 213R | 22 | PB | IM | 0-0 | 27-61-15 | D05131J | | 1 | | | TB0101H | 113 | 2 | | ALL |
| 214B | 22 | PB | IN | 2-8 | 27-61-15 | D01251A | | C01 | | | TB0101H | 115 | 2 | | ALL |
| 214R | 22 | PB | IN | 0-0 | 27-61-15 | D01251A | | A01 | | | TB0101H | 113 | 2 | | ALL |
| 215B | 22 | PB | IO | 2-9 | 27-61-15 | D00827B | | J07 | | | TB0101H | 115 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 5

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|-----|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0101 | 286T0101 | | | E1-1 SHELF (continued) | | | | | | | | | | | | | |
| 215R | 22 | PB | IO | | 0-0 | 27-61-15 | D00827B | | K07 | | | | TB0101H | 113 | 2 | | ALL |
| 216B | 22 | PB | IP | | 4-0 | 27-61-16 | D00829B | | J15 | | | | TB0101H | 115 | 2 | | ALL |
| 216R | 22 | PB | IP | | 0-0 | 27-61-16 | D00829B | | K15 | | | | TB0101H | 113 | 2 | | ALL |
| 217 | 20 | UA | | | 0-18 | 22-21-11 | D04353J | | | | FG | | GDX0007 | S.. | 2 | | ALL |
| 217B | 24 | PW | IQ | | 2-2 | 22-21-11 | D01259A | | K05 | | | | D04353J | 23 | | | ALL |
| 217R | 24 | PW | IQ | | 0-0 | 22-21-11 | D01259A | | K04 | | | | D04353J | 22 | | | ALL |
| 217Z | | | IQ | | 0-0 | 22-21-11 | D01259A | | DED | | | | D04353J | | | FG | ALL |
| 218B | 24 | PW | IR | | 4-2 | 22-21-11 | D01259A | | K15 | | | | TB0101G | 5 | 2 | | ALL |
| 218R | 24 | PW | IR | | 0-0 | 22-21-11 | D01259A | | K14 | | | | TB0101G | 4 | 2 | | ALL |
| 218Z | | | IR | | 0-0 | 22-21-11 | D01259A | | DED | | | | TB0101G | | | FC | ALL |
| 219B | 22 | PB | IS | | 2-3 | 27-41-11 | D00665A | | E10 | | | | D04353J | 7 | | | ALL |
| 219R | 22 | PB | IS | | 0-0 | 27-41-11 | D00665A | | E09 | | | | D04353J | 6 | | | ALL |
| 220 | 20 | UA | | | 0-18 | 27-11-12 | D04353J | | | | FH | | GDX0007 | S.. | 2 | | ALL |
| 220B | 24 | PW | IT | | 3-10 | 27-11-12 | TB0101G | | 5 | 2 | | | D04353J | 31 | | | ALL |
| 220R | 24 | PW | IT | | 0-0 | 27-11-12 | TB0101G | | 4 | 2 | | | D04353J | 30 | | | ALL |
| 220Z | | | IT | | 0-0 | 27-11-12 | D04353J | | | | FH | | TB0101G | | | FC | ALL |
| 222B | 24 | PW | IV | | 3-8 | 27-11-12 | D00665A | | D12 | | | | TB0101G | 5 | 2 | | ALL |
| 222R | 24 | PW | IV | | 0-0 | 27-11-12 | D00665A | | D11 | | | | TB0101G | 4 | 2 | | ALL |
| 222Z | | | IV | | 0-0 | 27-11-12 | D00665A | | DED | | | | TB0101G | | | FC | ALL |
| 223B | 22 | PB | IW | | 2-9 | 27-21-12 | D01263A | | D04 | | | | D00665A | K05 | | | ALL |
| 223R | 22 | PB | IW | | 0-0 | 27-21-12 | D01263A | | D05 | | | | D00665A | K04 | | | ALL |
| 302B | 22 | PC | MB | | 2-9 | 27-61-14 | D00825A | | J05 | | | | TB0101G | 10 | 2 | | ALL |
| 302R | 22 | PC | MB | | 0-0 | 27-61-14 | D00825A | | J03 | | | | TB0101G | 9 | 2 | | ALL |
| 302Y | 22 | PC | MB | | 0-0 | 27-61-14 | D00825A | | J04 | | | | TB0101G | 11 | 2 | | ALL |
| 303B | 22 | PC | MC | | 2-8 | 27-61-14 | D00825A | | K05 | | | | TB0101G | 111 | 2 | | ALL |
| 303R | 22 | PC | MC | | 0-0 | 27-61-14 | D00825A | | K03 | | | | TB0101G | 110 | 2 | | ALL |
| 303Y | 22 | PC | MC | | 0-0 | 27-61-14 | D00825A | | K04 | | | | TB0101G | 112 | 2 | | ALL |
| 304B | 22 | PC | MD | | 3-9 | 27-61-14 | D00825A | | K10 | | | | D05411J | 4 | | | ALL |
| 304R | 22 | PC | MD | | 0-0 | 27-61-14 | D00825A | | K08 | | | | D05411J | 5 | | | ALL |
| 304Y | 22 | PC | MD | | 0-0 | 27-61-14 | D00825A | | K09 | | | | D05411J | 7 | | | ALL |
| 305B | 22 | PC | ME | | 3-9 | 27-61-14 | D00825A | | J10 | | | | D05411J | 6 | | | ALL |
| 305R | 22 | PC | ME | | 0-0 | 27-61-14 | D00825A | | J08 | | | | D05411J | 12 | | | ALL |
| 305Y | 22 | PC | ME | | 0-0 | 27-61-14 | D00825A | | J09 | | | | D05411J | 13 | | | ALL |
| 306B | 22 | PC | MF | | 4-5 | 27-61-15 | D05131J | | 4 | | | | TB0101G | 10 | 2 | | ALL |
| 306R | 22 | PC | MF | | 0-0 | 27-61-15 | D05131J | | 6 | | | | TB0101G | 9 | 2 | | ALL |
| 306Y | 22 | PC | MF | | 0-0 | 27-61-15 | D05131J | | 7 | | | | TB0101G | 11 | 2 | | ALL |
| 307B | 22 | PC | MG | | 4-4 | 27-61-15 | D05131J | | 15 | | | | TB0101G | 111 | 2 | | ALL |
| 307R | 22 | PC | MG | | 0-0 | 27-61-15 | D05131J | | 3 | | | | TB0101G | 110 | 2 | | ALL |
| 307Y | 22 | PC | MG | | 0-0 | 27-61-15 | D05131J | | 5 | | | | TB0101G | 112 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 6

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0101 | 286T0101 | | | | | E1-1 SHELF (continued) | | | | | | | | | |
| 308B | 22 | PC | MH | | 4-6 | 27-61-16 | D00829B | | J14 | | TB0101G | 10 | 2 | | ALL |
| 308R | 22 | PC | MH | | 0-0 | 27-61-16 | D00829B | | J12 | | TB0101G | 9 | 2 | | ALL |
| 308Y | 22 | PC | MH | | 0-0 | 27-61-16 | D00829B | | J13 | | TB0101G | 11 | 2 | | ALL |
| 309B | 22 | PC | MI | | 4-5 | 27-61-16 | D00829B | | K14 | | TB0101G | 111 | 2 | | ALL |
| 309R | 22 | PC | MI | | 0-0 | 27-61-16 | D00829B | | K12 | | TB0101G | 110 | 2 | | ALL |
| 309Y | 22 | PC | MI | | 0-0 | 27-61-16 | D00829B | | K13 | | TB0101G | 112 | 2 | | ALL |
| 312B | 22 | PC | ML | | 3-2 | 27-61-15 | D00827B | | J06 | | TB0101G | 10 | 2 | | ALL |
| 312R | 22 | PC | ML | | 0-0 | 27-61-15 | D00827B | | J04 | | TB0101G | 9 | 2 | | ALL |
| 312Y | 22 | PC | ML | | 0-0 | 27-61-15 | D00827B | | J05 | | TB0101G | 11 | 2 | | ALL |
| 313B | 22 | PC | MM | | 3-1 | 27-61-15 | D00827B | | K06 | | TB0101G | 111 | 2 | | ALL |
| 313R | 22 | PC | MM | | 0-0 | 27-61-15 | D00827B | | K04 | | TB0101G | 110 | 2 | | ALL |
| 313Y | 22 | PC | MM | | 0-0 | 27-61-15 | D00827B | | K05 | | TB0101G | 112 | 2 | | ALL |
| 314B | 22 | PC | MN | | 3-10 | 22-21-11 | D01259A | | K02 | | D01251A | K06 | | | ALL |
| 314R | 22 | PC | MN | | 0-0 | 22-21-11 | D01259A | | K01 | | D01251A | K05 | | | ALL |
| 314Y | 22 | PC | MN | | 0-0 | 22-21-11 | D01259A | | J01 | | D01251A | J05 | | | ALL |
| 315B | 22 | PC | M0 | | 3-10 | 22-21-11 | D01259A | | H01 | | D01251A | J06 | | | ALL |
| 315R | 22 | PC | M0 | | 0-0 | 22-21-11 | D01259A | | J02 | | D01251A | K07 | | | ALL |
| 315Y | 22 | PC | M0 | | 0-0 | 22-21-11 | D01259A | | H02 | | D01251A | J07 | | | ALL |
| 316B | 22 | PC | MP | | 2-11 | 22-21-11 | D01259A | | G02 | | D01253A | K06 | | | ALL |
| 316R | 22 | PC | MP | | 0-0 | 22-21-11 | D01259A | | G01 | | D01253A | K05 | | | ALL |
| 316Y | 22 | PC | MP | | 0-0 | 22-21-11 | D01259A | | F01 | | D01253A | J05 | | | ALL |
| 317B | 22 | PC | MQ | | 2-11 | 22-21-11 | D01259A | | E01 | | D01253A | J06 | | | ALL |
| 317R | 22 | PC | MQ | | 0-0 | 22-21-11 | D01259A | | F02 | | D01253A | K07 | | | ALL |
| 317Y | 22 | PC | MQ | | 0-0 | 22-21-11 | D01259A | | E02 | | D01253A | J07 | | | ALL |
| 318B | 22 | PC | MR | | 3-5 | 27-41-11 | D00665A | | H05 | | D01251A | H06 | | | ALL |
| 318R | 22 | PC | MR | | 0-0 | 27-41-11 | D00665A | | H04 | | D01251A | H05 | | | ALL |
| 318Y | 22 | PC | MR | | 0-0 | 27-41-11 | D00665A | | H06 | | D01251A | G05 | | | ALL |
| 319B | 22 | PC | MS | | 3-5 | 27-41-11 | D00665A | | J05 | | D01251A | G06 | | | ALL |
| 319R | 22 | PC | MS | | 0-0 | 27-41-11 | D00665A | | J04 | | D01251A | H07 | | | ALL |
| 319Y | 22 | PC | MS | | 0-0 | 27-41-11 | D00665A | | J06 | | D01251A | G07 | | | ALL |
| 320B | 22 | PC | MT | | 3-5 | 27-41-11 | D00665A | | F05 | | D01253A | H06 | | | ALL |
| 320R | 22 | PC | MT | | 0-0 | 27-41-11 | D00665A | | F04 | | D01253A | H05 | | | ALL |
| 320Y | 22 | PC | MT | | 0-0 | 27-41-11 | D00665A | | F06 | | D01253A | G05 | | | ALL |
| 321B | 22 | PC | MU | | 3-5 | 27-41-11 | D00665A | | G05 | | D01253A | G06 | | | ALL |
| 321R | 22 | PC | MU | | 0-0 | 27-41-11 | D00665A | | G04 | | D01253A | H07 | | | ALL |
| 321Y | 22 | PC | MU | | 0-0 | 27-41-11 | D00665A | | G06 | | D01253A | G07 | | | ALL |
| 500 | 22 | PA | | | 3-3 | 22-21-11 | D01259A | | A04 | | GDX0001 | D.. | 2 | | 150-199, 275-299 |
| 601Y | 22 | PJ | | | 2-8 | 27-41-11 | D11810 | | A2 | | D05131J | 16 | | | ALL |
| 602 | 22 | PA | | | 2-1 | 27-41-11 | D11810 | | X2 | | D04353J | 35 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0100
 Page 7
 Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------|----|-------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0101 | 286T0101 | | | E1-1 SHELF (continued) | | | | | | | | | | | | |
| 603 | 22 | | PA | | 3-1 | 27-41-11 | D11810 | | X1 | | TB0101H | 117 | 2 | | ALL | |
| 604Y | 22 | | PJ | | 2-1 | 27-41-11 | D11810 | | A3 | | D04353J | 36 | | | 050-099 | |
| 604Y | 22 | | PJ | | 2-1 | 27-41-11 | D11810 | | A1 | | D04353J | 36 | | | 150-199, 275-299 | |
| 605Y | 22 | | PJ | | 2-1 | 27-41-11 | D11810 | | A1 | | D04353J | 16 | | | 050-099 | |
| 605Y | 22 | | PJ | | 2-1 | 27-41-11 | D11810 | | A3 | | D04353J | 16 | | | 150-199, 275-299 | |
| 706 | 22 | | PA | | 2-3 | 22-22-11 | D00665A | | D10 | | D04353J | 1 | | | ALL | |
| 707 | 22 | | PA | | 2-3 | 22-22-11 | D00665A | | D09 | | D04353J | 12 | | | ALL | |
| 70L | 20 | | PA | | 3-9 | 29-11-14 | D04353J | | 37 | | TB0101G | 107 | 2 | | ALL | |
| 70M | 20 | | PQ | CT | 3-10 | 29-11-14 | D04353J | | 41 | | TB0101G | 8 | 2 | | ALL | |
| 70MZ | | | | CT | 0-0 | 29-11-14 | D04353J | | DED | | TB0101G | DED | | | 050-099, 150-199, 275-278 | |
| 70MZ | | | | CT | 0-0 | 29-11-14 | D04353J | | DED | | TB0101Z | DED | | | 280-299 | |
| 837 | 24 | | PK | | 3-9 | 31-31-15 | D04353J | | 14 | | TB0101G | 102 | 2 | | 050-099, 155-199, 275-299 | |
| FRG | | | | | 0-0 | 22-21-11 | D04353J | | 21 | | D04353J | | | | FG ALL | |
| FRH | | | | | 0-0 | 27-11-12 | D04353J | | 29 | | D04353J | | | | FH ALL | |
| FRK | | | | | 0-0 | 22-22-11 | D04353J | | 27 | | D04353J | | | | FK ALL | |
| W0102 | 286T0102 | | | FWD CABIN RIGHT | | | | | | | | | | | | |
| 001 | 22 | | PA | | 7-0 | 23-42-11 | D04397P | | 1 | | L00745 | = P | \$ | | 050-099, 150-199 | |
| 002 | 22 | | PA | | 7-0 | 23-34-13 | D04397P | | 2 | | L00864 | = P | \$ | | 050-099, 150-199 | |
| 003 | 22 | | PA | | 7-0 | 33-25-11 | D04397P | | 3 | | L00747 | = P | \$ | | 050-099, 150-199 | |
| 004 | 20 | | PA | | 7-0 | 23-42-11 | D04397P | | 4 | | L00745 | = G | \$ | | 050-099, 150-199 | |
| 051 | 22 | | PA | | 6-0 | 23-42-11 | D05329P | | 1 | | L00195 | = P | \$ | | 150 | |
| 051 | 22 | | PA | | 6-0 | 23-42-11 | D05329P | | 1 | | L00195 | L1 | C | | 151-157 | |
| 051 | 22 | | PA | | 7-0 | 23-42-11 | D05329P | | 1 | | L00195 | = P | \$ | | 275-299 | |
| 052 | 22 | | PA | | 6-0 | 23-34-13 | D05329P | | 2 | | L00580 | = P | \$ | | 150 | |
| 052 | 22 | | PA | | 6-0 | 23-34-13 | D05329P | | 2 | | L00580 | L3 | C | | 151-157 | |
| 052 | 22 | | PA | | 7-0 | 23-34-13 | D05329P | | 2 | | L00580 | = P | \$ | | 275-299 | |
| 053 | 22 | | PA | | 6-0 | 33-25-11 | D05329P | | 3 | | L00564 | = P | \$ | | 150 | |
| 053 | 22 | | PA | | 6-0 | 33-25-11 | D05329P | | 3 | | L00564 | L2 | C | | 151-157 | |
| 053 | 22 | | PA | | 7-0 | 33-25-11 | D05329P | | 3 | | L00564 | = P | \$ | | 275-299 | |
| 054 | 20 | | PA | | 6-0 | 23-42-11 | D05329P | | 4 | | L00195 | = G | \$ | | 150 | |
| 054 | 20 | | PA | | 6-0 | 23-42-11 | D05329P | | 4 | | L00195 | 3 | C | | 151-157 | |
| 054 | 20 | | PA | | 7-0 | 23-42-11 | D05329P | | 4 | | L00195 | = G | \$ | | 275-299 | |
| W0104 | 286T0104 | | | FWD CABIN LEFT | | | | | | | | | | | | |
| 051 | 22 | | PA | | 3-0 | 23-42-11 | D05327P | | 1 | | L00194 | = P | \$ | | 150, 275-299 | |
| 051 | 22 | | PA | | 3-0 | 23-42-11 | D05327P | | 1 | | L00194 | L1 | C | | 151-157 | |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 8

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0104 | 286T0104 | | | FWD CABIN LEFT (continued) | | | | | | | | | | | |
| 052 | 22 | | PA | | 3-0 | 23-34-13 | D05327P | | 2 | | L00579 | =P | \$ | | 150, 275-299 |
| 052 | 22 | | PA | | 3-0 | 23-34-13 | D05327P | | 2 | | L00579 | L3 | C | | 151-157 |
| 053 | 22 | | PA | | 3-0 | 33-25-11 | D05327P | | 3 | | L00565 | =P | \$ | | 150, 275-299 |
| 053 | 22 | | PA | | 3-0 | 33-25-11 | D05327P | | 3 | | L00565 | L2 | C | | 151-157 |
| 054 | 20 | | PA | | 3-0 | 23-42-11 | D05327P | | 4 | | L00194 | =G | \$ | | 150, 275-299 |
| 054 | 20 | | PA | | 3-0 | 23-42-11 | D05327P | | 4 | | L00194 | 3 | C | | 151-157 |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE | | | | | | | | | | | |
| 001 | 22 | | PQ | AA | 3-5 | 22-11-12 | D00433C | | 1 | | TB0105H | 125 | 2 | | ALL |
| 001Z | | | | AA | 0-0 | 22-11-12 | D00433C | DED | | | TB0105H | DED | | | ALL |
| 002 | 20 | | PQ | AB | 3-5 | 22-11-12 | D00433C | | 2 | | TB0105H | 125 | 2 | | ALL |
| 002Z | | | | AB | 0-0 | 22-11-12 | D00433C | DED | | | TB0105H | DED | | | ALL |
| 003 | 22 | | PA | | 4-0 | 22-11-12 | D04207P | | 3 | | TB0105G | 25 | 2 | | ALL |
| 004 | 20 | | PA | | 2-4 | 22-11-11 | D00433C | | 4 | | GDX0004 | A.. | 2 | | ALL |
| 005 | 22 | | PQ | AE | 3-5 | 22-11-12 | D00433C | | 5 | | TB0105H | 125 | 2 | | ALL |
| 005Z | | | | AE | 0-0 | 22-11-12 | D00433C | DED | | | TB0105H | DED | | | ALL |
| 006 | 22 | | PA | | 3-8 | 22-11-11 | D00433C | | 6 | | D04207P | 1 | | | ALL |
| 007 | 20 | | PA | | 2-4 | 22-11-11 | D00433C | | 7 | | GDX0004 | S.. | 2 | | ALL |
| 008 | 22 | | PQ | AH | 3-10 | 22-11-12 | D04207P | | 2 | | TB0105H | 125 | 2 | | ALL |
| 008Z | | | | AH | 0-0 | 22-11-12 | D04207P | DED | | | TB0105H | DED | | | ALL |
| 009 | 20 | | PA | | 3-5 | 22-11-12 | D00433C | | 9 | | TB0105F | A122 | 2 | | ALL |
| 010 | 22 | | PA | | 4-1 | 22-11-12 | D04591P | | 3 | | TB0105G | 29 | 2 | | ALL |
| 011 | 22 | | PA | | 4-0 | 22-11-12 | D04591P | | 1 | | TB0105G | 25 | 2 | | ALL |
| 012 | 22 | | PA | | 3-8 | 22-11-12 | D00433A | H15 | | | TB0105G | 29 | 2 | | ALL |
| 013 | 22 | | PA | | 3-8 | 22-11-12 | D00433B | H15 | | | TB0105G | 29 | 2 | | ALL |
| 015 | 22 | | PA | | 3-10 | 22-11-12 | D00433B | F15 | | | D04365P | 30 | | | ALL |
| 017 | 22 | | PA | | 4-2 | 22-11-12 | D04365P | | 10 | | TB0105H | 21 | 2 | | ALL |
| 018 | 22 | | PA | | 3-7 | 22-11-12 | D00433B | H11 | | | TB0105H | 21 | 2 | | ALL |
| 019 | 22 | | PA | | 4-2 | 22-11-12 | D04365P | | 15 | | TB0105H | 21 | 2 | | ALL |
| 020 | 24 | | PK | | 0-7 | 22-11-12 | D00433B | A03 | | | D00433B | E04 | | | ALL |
| 021 | 20 | | PA | | 3-1 | 22-11-12 | D04365P | | 4 | | GDX0003 | D.. | 2 | | ALL |
| 022 | 20 | | PA | | 3-1 | 22-11-12 | D04365P | | 46 | | GDX0003 | D.. | 2 | | ALL |
| 023 | 22 | | PQ | AW | 3-10 | 22-11-12 | D04591P | | 2 | | TB0105H | 125 | 2 | | ALL |
| 023Z | | | | AW | 0-0 | 22-11-12 | D04591P | DED | | | TB0105H | DED | | | ALL |
| 024 | 24 | | PK | | 3-2 | 22-11-12 | D00433B | A06 | | | D05605J | 29 | | | ALL |
| 025 | 24 | | PK | | 3-2 | 22-11-12 | D00433B | C07 | | | D05605J | 30 | | | ALL |
| 026 | 22 | | PA | | 3-10 | 22-11-12 | D00433A | C15 | | | D04383P | 14 | | | ALL |
| 027 | 22 | | PA | | 3-10 | 22-11-12 | D00433B | C15 | | | D04383P | 11 | | | ALL |
| 028 | 22 | | PA | | 3-1 | 22-11-12 | D00433B | A15 | | | D04379P | 1 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0100
 Page 9
 Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | | |
| 029 | 22 | | PA | 3-1 | 22-11-12 | D00433A | A15 | | | | D04379P | 52 | | | ALL | |
| 030 | 24 | | PK | 0-7 | 22-11-12 | D00433A | A13 | | | | D00433A | A14 | | | ALL | |
| 031 | 22 | | PA | 2-4 | 22-11-12 | D00433A | A04 | | | | GDX0004 | D.. | 2 | | ALL | |
| 032 | 22 | | PA | 2-4 | 22-11-12 | D00433A | G11 | | | | GDX0004 | D.. | 2 | | ALL | |
| 034 | 22 | | PA | 3-1 | 22-11-12 | D00433B | K15 | | | | D04379P | 37 | | | ALL | |
| 035 | 22 | | PA | 3-1 | 22-11-12 | D00433A | K15 | | | | D04379P | 49 | | | ALL | |
| 037 | 24 | | PK | 3-7 | 32-42-11 | D04169P | 24 | | | | D04457P | 30 | | | ALL | |
| 038 | 22 | | PA | 4-6 | 22-12-11 | D04365P | 41 | | | | TB0105G | 39 | 2 | | ALL | |
| 039 | 22 | | PA | 3-11 | 22-12-11 | D00433A | F15 | | | | TB0105G | 39 | 2 | | ALL | |
| 040 | 22 | | PA | 3-1 | 22-12-11 | D04365P | 42 | | | | GDX0003 | D.. | 2 | | ALL | |
| 041 | 22 | | PA | 3-10 | 22-12-11 | D04365P | 43 | | | | D00433B | E09 | | | ALL | |
| 042 | 24 | | PK | 4-4 | 34-46-12 | D04367P | 28 | | | | D04855P | 7 | | | ALL | |
| 043 | 24 | | PK | 4-3 | 22-12-11 | D04417P | 6 | | | | D00433B | E10 | | | ALL | |
| 044 | 24 | | PK | 4-10 | 22-14-11 | D04855P | 16 | | | | D00433B | K10 | | | ALL | |
| 045 | 24 | | PK | 4-1 | 22-13-11 | D00433B | H03 | | | | TB0105G | 48 | 2 | | ALL | |
| 046 | 22 | | PA | 3-5 | 22-14-11 | D00433A | F03 | | | | TB0105F | C122 | 2 | | ALL | |
| 048 | 24 | | PK | 0-7 | 22-11-12 | D00433B | C13 | | | | D00433B | F04 | | | 150-156, 162-166 | |
| 048 | 24 | | PK | 0-7 | 22-11-12 | D00433B | F04 | | | | D00433B | C13 | | | 157, 167-199, 277-299 | |
| 049 | 24 | | PK | 4-10 | 22-14-11 | D00433B | K11 | | | | D04855P | 18 | | | ALL | |
| 050 | 24 | | PK | 4-10 | 22-14-11 | D00433B | K03 | | | | D04855P | 19 | | | ALL | |
| 051 | 24 | | PK | 3-2 | 22-14-11 | D00433B | K12 | | | | D05605J | 31 | | | ALL | |
| 052 | 22 | | PA | 3-10 | 22-14-11 | D04169P | 5 | | | | TB0105G | 25 | 2 | | ALL | |
| 053 | 24 | | PK | 3-5 | 22-14-11 | D00433B | E12 | | | | TB0105H | 19 | 2 | | ALL | |
| 054 | 24 | | PK | 3-4 | 22-14-11 | D04323P | 1 | | | | TB0105H | 19 | 2 | | ALL | |
| 055 | 24 | | PK | 6-0 | 22-14-11 | D00433A | E12 | | | | TB0105H | 188 | 2 | | ALL | |
| 056 | 22 | | PA | 3-0 | 31-31-25 | D04337P | 22 | | | | D05247P | 21 | | | 050-099, 150-199 | |
| 057 | 24 | | PK | 4-10 | 22-14-11 | D00433B | J11 | | | | D04855P | 21 | | | ALL | |
| 058 | 24 | | PK | 3-6 | 22-14-11 | D00433B | K02 | | | | TB0105G | 116 | 2 | | ALL | |
| 059 | 24 | | PK | 3-2 | 22-14-11 | D00433B | J12 | | | | D05605J | 33 | | | ALL | |
| 060 | 22 | | PA | 3-8 | 22-14-11 | D00433A | C13 | | | | TB0105G | 30 | 2 | | ALL | |
| 061 | 24 | | PK | 0-7 | 22-11-12 | D00433B | K13 | | | | D00433B | K14 | | | ALL | |
| 062 | 24 | | PK | 3-5 | 22-14-11 | D00433B | G12 | | | | TB0105G | 118 | 2 | | ALL | |
| 063 | 24 | | PK | 3-5 | 22-14-11 | D00433A | G12 | | | | TB0105F | A117 | 2 | | ALL | |
| 064 | 24 | | PK | 4-5 | 22-14-31 | D04855P | 40 | | | | TB0105H | 19 | 2 | | ALL | |
| 065 | 24 | | PV | CO | 3-5 | 22-15-12 | D00433A | E03 | | | TB0105F | C119 | 2 | | ALL | |
| 065Z | | | CO | CO | 0-0 | 22-15-12 | D00433A | DED | | | TB0105F | DED | | | ALL | |
| 066 | 22 | | PA | 5-2 | 22-14-21 | D04855P | 20 | | | | TB0105G | 30 | 2 | | ALL | |
| 068 | 22 | | PA | 4-6 | 22-14-31 | D04457P | 1 | | | | TB0105G | 30 | 2 | | ALL | |
| 069 | 24 | | PK | 3-6 | 22-15-12 | D05605J | 14 | | | | TB0105G | 109 | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 10

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 070 | 22 | | PA | | 2-8 | 22-14-31 | D05605J | | | 15 | TB0105G | 30 | 2 | | ALL |
| 071 | 22 | | PA | | 3-1 | 22-14-31 | D04457P | | | 2 | D05603P | 4 | | | ALL |
| 073 | 24 | | PK | | 3-4 | 22-14-31 | D05605J | | | 17 | TB0105H | 19 | 2 | | ALL |
| 074 | 24 | | PK | | 3-7 | 22-15-12 | D00433A | | K01 | | TB0105F | A135 | 2 | | ALL |
| 075 | 24 | | PK | | 4-3 | 22-15-12 | D00433A | | G10 | | TB0105G | 59 | 2 | | ALL |
| 076 | 24 | | PK | | 3-3 | 22-15-12 | D05605J | | | 21 | TB0105G | 59 | 2 | | ALL |
| 077 | 24 | | PK | | 6-4 | 22-15-12 | D04855P | | | 12 | TB0105G | 59 | 2 | | ALL |
| 078 | 24 | | PK | | 3-5 | 22-15-12 | D00433A | | K03 | | TB0105F | A119 | 2 | | ALL |
| 079 | 24 | | PK | | 3-6 | 22-15-12 | D05605J | | | 16 | TB0105G | 109 | 2 | | ALL |
| 080 | 24 | | PK | | 3-1 | 22-12-11 | D00433A | | F12 | | D04351P | 11 | | | ALL |
| 081 | 22 | | PA | | 4-4 | 22-22-11 | D04351P | | | 2 | TB0105G | 64 | 2 | | ALL |
| 082 | 24 | | PK | | 4-6 | 22-12-11 | D00433B | | G09 | | TB0105G | 64 | 2 | | ALL |
| 083 | 24 | | PK | | 4-6 | 22-12-11 | D00433A | | G09 | | TB0105G | 64 | 2 | | ALL |
| 084 | 24 | | PK | | 4-2 | 22-41-11 | D00433B | | C06 | | D04457P | 52 | | | ALL |
| 085 | 24 | | PK | | 3-1 | 22-41-11 | D00433A | | A03 | | D05603P | 8 | | | ALL |
| 086 | 20 | | PA | | 3-1 | 22-11-12 | D04365P | | | 25 | GDX0003 | D.. | 2 | | ALL |
| 089 | 24 | | PK | | 3-7 | 22-12-11 | D04367P | | | 22 | D00433B | D08 | | | ALL |
| 090 | 24 | | PK | | 3-7 | 22-12-11 | D04367P | | | 23 | D00433B | C09 | | | ALL |
| 091 | 24 | | PK | | 6-0 | 34-46-12 | D04457P | | | 3 | D04855P | 45 | | | ALL |
| 092 | 24 | | PK | | 4-0 | 22-13-11 | D04169P | | | 16 | TB0105G | 31 | 2 | | ALL |
| 093 | 24 | | PK | | 3-8 | 22-13-11 | D00433B | | H02 | | TB0105G | 31 | 2 | | ALL |
| 094 | 22 | | PA | | 3-6 | 34-22-16 | D05603P | | | 53 | TB0105G | 31 | 2 | | ALL |
| 095 | 24 | | PK | | 3-7 | 22-41-13 | D00433B | | F10 | | D04169P | 30 | | | ALL |
| 096 | 24 | | PK | | 3-7 | 22-41-13 | D00433B | | F09 | | D04169P | 15 | | | ALL |
| 097 | 22 | | PA | | 2-10 | 27-41-11 | D04365P | | | 29 | D04351P | 12 | | | 150-154 |
| 099 | 22 | | PA | | 2-7 | 27-61-11 | D04367P | | | 16 | D04351P | 19 | | | ALL |
| 101 | 20 | | PA | | 4-8 | 34-31-11 | D04207P | | | 11 | D00429C | 2 | | | ALL |
| 102 | 20 | | PA | | 2-8 | 34-31-11 | GDX0007 | | A.. | 2 | D00429C | 3 | | | ALL |
| 103 | 20 | | PA | | 2-8 | 34-31-11 | GDX0007 | | D.. | 2 | D00429C | 4 | | | ALL |
| 104 | 24 | | PK | | 0-7 | 34-31-11 | D00429B | | B03 | | D00429B | C03 | | | ALL |
| 105 | 24 | | PK | | 0-7 | 34-31-11 | D00429B | | B05 | | D00429B | C05 | | | ALL |
| 106 | 22 | | PA | | 2-10 | 34-61-14 | D04781P | | | 55 | TB0105G | 31 | 2 | | ALL |
| 107 | 22 | | PA | | 4-7 | 34-31-11 | D04365P | | | 5 | TB0105G | 48 | 2 | | ALL |
| 108 | 22 | | PA | | 2-10 | 34-31-11 | D04365P | | | 11 | D05603P | 46 | | | ALL |
| 109 | 24 | | PK | | 3-3 | 22-13-11 | D00429B | | C01 | | TB0105G | 48 | 2 | | ALL |
| 110 | 24 | | PK | | 3-10 | 34-31-11 | D00429B | | D15 | | TB0105G | 71 | 2 | | ALL |
| 111 | 24 | | PK | | 6-3 | 34-57-11 | D04417P | | | 11 | TB0105G | 71 | 2 | | ALL |
| 112 | 24 | | PK | | 3-11 | 34-55-11 | D04781P | | | 27 | TB0105G | 71 | 2 | | ALL |
| 113 | 24 | | PK | | 6-1 | 34-55-11 | D04457P | | | 26 | TB0105G | 71 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 11

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | | | |
| 114 | 24 | | PK | 3-7 | 22-12-11 | D04367P | | 24 | | | | | D00433B | D10 | | | ALL |
| 115 | 24 | | PK | 3-7 | 22-12-11 | D04367P | | 25 | | | | | D00433B | D09 | | | ALL |
| 122 | 24 | | PK | 3-2 | 27-48-11 | D05247P | | 37 | | | | | TB0105G | 9 | 2 | | 157, 167-199, 277-299 |
| 123 | 24 | | PK | 3-2 | 27-48-11 | D05247P | | 38 | | | | | TB0105G | 8 | 2 | | 157, 167-199, 277-299 |
| 125 | 22 | | PA | 4-0 | 34-12-61 | D03691P | | 2 | | | | | TB0105D | C001 | 2 | | ALL |
| 126 | 22 | | PA | 4-0 | 34-12-61 | D03691P | | 1 | | | | | TB0105D | A001 | 2 | | ALL |
| 127 | 20 | | PA | 4-0 | 34-12-61 | TB0105D | | A001 | 2 | | | | GD0002 | D.. | 2 | | ALL |
| 128 | 24 | | PK | 4-0 | 34-12-61 | D03691P | | 11 | | | | | TB0105G | 2 | 2 | | ALL |
| 129 | 20 | | PQ | FD | 6-6 | 22-31-12 | | 2 | | | | | D04207P | 6 | | | ALL |
| 129Z | | | | FD | 0-0 | 22-31-12 | | DED | | | | | D04207P | DED | | | ALL |
| 130 | 20 | | PQ | FE | 6-6 | 22-31-12 | | 9 | | | | | D04207P | 5 | | | ALL |
| 130Z | | | | FE | 0-0 | 22-31-12 | | DED | | | | | D04207P | DED | | | ALL |
| 131 | 22 | | PA | | 5-1 | 34-45-12 | | E08 | | | | | TB0105H | 112 | 2 | | ALL |
| 132 | 22 | | PA | | 5-1 | 34-45-12 | | B07 | | | | | TB0105H | 112 | 2 | | ALL |
| 133 | 22 | | PA | | 5-1 | 34-45-12 | | K07 | | | | | TB0105H | 112 | 2 | | ALL |
| 134 | 22 | | PA | | 7-3 | 34-45-12 | | B05 | | | | | D06143P | 7 | | | 050-099, 150-152, 155-199, 275-299 |
| 134 | 22 | | PA | | 6-7 | 34-45-12 | | B05 | | | | | D05259P | 22 | | | 153-154 |
| 135 | 22 | | PA | | 7-3 | 34-45-12 | | D05 | | | | | D06143P | 8 | | | 050-099, 150-152, 155-199, 275-299 |
| 135 | 22 | | PA | | 6-7 | 34-45-12 | | D05 | | | | | D05259P | 23 | | | 153-154 |
| 137 | 22 | | PA | | 6-0 | 34-45-14 | | 25 | | | | | TB0105G | CAP | Y | | 157, 167-199, 277-299 |
| 138 | 22 | | PA | | 6-0 | 34-45-14 | | 26 | | | | | TB0105G | CAP | Y | | 157, 167-199, 277-299 |
| 139 | 24 | | PK | | 0-7 | 22-11-12 | | D03 | | | | | D00433B | K04 | | | ALL |
| 140 | 22 | | PA | | 6-0 | 34-45-14 | | 9 | | | | | TB0105G | CAP | Y | | 157, 167-199, 277-299 |
| 141 | 22 | | PA | | 3-11 | 34-45-14 | | C14 | | | | | TB0105G | 47 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 141 | 22 | | PA | | 3-8 | 34-45-14 | | C14 | | | | | TB0105G | 54 | 2 | | 157, 167-199, 277-299 |
| 143 | 20 | | PA | | 2-4 | 27-48-11 | | 4 | | | | | GD0003 | A.. | 2 | | 157, 167-199, 277-299 |
| 144 | 24 | | PK | | 0-7 | 22-11-12 | | F11 | | | | | D00433B | K09 | | | 050-099, 150-156, 162-166 |
| 144 | 24 | | PK | | 0-7 | 22-11-12 | | K09 | | | | | D00433B | F11 | | | 157, 167-199, 277-299 |
| 146 | 22 | | PA | | 5-0 | 34-12-61 | | 6 | | | | | D05259P | 10 | | | ALL |
| 147 | 22 | | PA | | 5-0 | 34-12-61 | | 5 | | | | | D05259P | 11 | | | ALL |
| 150 | 24 | | PK | | 4-0 | 34-12-61 | | 10 | | | | | TB0105H | 107 | 2 | | ALL |
| 153 | 24 | | PK | | 3-4 | 22-32-13 | | G11 | | | | | TB0105F | A094 | 2 | | ALL |
| 154 | 24 | | PK | | 3-4 | 22-32-13 | | E03 | | | | | TB0105F | C094 | 2 | | ALL |
| 155 | 24 | | PK | | 3-4 | 22-32-13 | | G04 | | | | | TB0105F | A095 | 2 | | ALL |
| 156 | 24 | | PK | | 3-4 | 22-32-13 | | D04 | | | | | TB0105F | C095 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 12

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 157 | 22 | PA | | 3-3 | 22-32-13 | D00427B | E10 | | | GDX0011 | S.. | 2 | | ALL | |
| 158 | 22 | PA | | 3-3 | 22-32-13 | D00427B | J01 | | | GDX0011 | S.. | 2 | | ALL | |
| 159 | 22 | PA | | 3-3 | 22-32-13 | D00427B | E02 | | | GDX0011 | S.. | 2 | | ALL | |
| 160 | 24 | PK | | 3-8 | 22-15-12 | D00433A | F09 | | | TB0105G | 109 | 2 | | ALL | |
| 161 | 20 | PA | | 2-10 | 27-41-11 | D04365P | 33 | | | D04379P | 26 | | | ALL | |
| 162 | 20 | PA | | 2-10 | 27-41-11 | D04365P | 28 | | | D04379P | 27 | | | ALL | |
| 163 | 24 | PV | GM | 3-5 | 22-15-12 | D00433A | G01 | | | TB0105F | C117 | 2 | | ALL | |
| 163Z | | | GM | 0-0 | 22-15-12 | D00433A | DED | | | TB0105F | DED | | | ALL | |
| 165Y | 22 | PJ | | 2-10 | 27-41-11 | D04365P | 2 | | | D04379P | 40 | | | 050-099, 275-299 | |
| 165Y | 22 | PJ | | 3-7 | 27-41-11 | D04337P | 21 | | | D04379P | 40 | | | 150-199 | |
| 167Y | 22 | PJ | | 2-10 | 27-41-11 | D04351P | 1 | | | D04379P | 28 | | | ALL | |
| 168Y | 22 | PJ | | 2-10 | 27-41-11 | D04365P | 49 | | | D04379P | 29 | | | 050-099 | |
| 170 | 24 | PK | | 3-2 | 27-48-11 | D04207P | 12 | | | TB0105G | 10 | 2 | | ALL | |
| 171 | 24 | PK | | 3-2 | 27-48-11 | D04365P | 21 | | | TB0105G | 10 | 2 | | ALL | |
| 172 | 24 | PK | | 3-1 | 27-48-11 | D04365P | 36 | | | TB0105G | 9 | 2 | | ALL | |
| 173 | 24 | PK | | 3-1 | 27-48-11 | D04365P | 37 | | | TB0105G | 8 | 2 | | ALL | |
| 174 | 24 | PK | | 2-8 | 27-48-11 | D04379P | 41 | | | TB0105G | 10 | 2 | | ALL | |
| 175 | 24 | PK | | 2-9 | 27-48-11 | D04379P | 42 | | | TB0105G | 9 | 2 | | ALL | |
| 176 | 24 | PK | | 2-9 | 27-48-11 | D04379P | 43 | | | TB0105G | 8 | 2 | | ALL | |
| 180 | 24 | PK | | 3-9 | 31-51-42 | D04323P | 6 | | | D04365P | 48 | | | ALL | |
| 182 | 24 | PK | | 7-2 | 34-33-11 | D05383P | 5 | | | D04417P | 5 | | | ALL | |
| 183 | 24 | PK | | 7-2 | 34-33-21 | D05383P | 4 | | | D04417P | 4 | | | ALL | |
| 184 | 24 | PK | | 7-2 | 34-33-31 | D04417P | 10 | | | D05383P | 10 | | | ALL | |
| 185 | 22 | PA | | 2-7 | 22-24-11 | D04351P | 23 | | | D04367P | 1 | | | ALL | |
| 188 | 24 | PK | | 4-9 | 34-12-22 | D05383P | 6 | | | TB0105G | 138 | 2 | | ALL | |
| 190 | 24 | PK | | 4-7 | 34-12-12 | D00423B | E07 | | | D04855P | 33 | | | 275-299 | |
| 191 | 24 | PK | | 3-2 | 34-12-12 | D05247P | 29 | | | TB0105H | 107 | 2 | | ALL | |
| 194 | 22 | PA | | 7-0 | 31-31-14 | D04855P | 55 | | | D04351P | 24 | | | ALL | |
| 199 | 20 | PA | | 2-10 | 27-21-11 | D04365P | 45 | | | D04379P | 38 | | | ALL | |
| 204B | 20 | PB | ID | 3-8 | 22-11-11 | D00433C | 11 | | | TB0105H | 32 | 2 | | ALL | |
| 204R | 20 | PB | ID | 0-0 | 22-11-11 | D00433C | 10 | | | TB0105H | 34 | 2 | | ALL | |
| 205B | 22 | PB | IE | 3-6 | 22-11-11 | D04383P | 2 | | | TB0105H | 32 | 2 | | ALL | |
| 205R | 22 | PB | IE | 0-0 | 22-11-11 | D04383P | 1 | | | TB0105H | 34 | 2 | | ALL | |
| 206B | 22 | PB | IF | 3-6 | 22-11-11 | D04379P | 6 | | | TB0105H | 32 | 2 | | ALL | |
| 206R | 22 | PB | IF | 0-0 | 22-11-11 | D04379P | 5 | | | TB0105H | 34 | 2 | | ALL | |
| 207B | 22 | PB | IG | 3-6 | 22-11-11 | D04379P | 8 | | | TB0105H | 32 | 2 | | ALL | |
| 207R | 22 | PB | IG | 0-0 | 22-11-11 | D04379P | 7 | | | TB0105H | 34 | 2 | | ALL | |
| 208B | 24 | PW | IH | 3-7 | 22-12-11 | D00433B | B04 | | | TB0105G | 24 | 2 | | ALL | |
| 208R | 24 | PW | IH | 0-0 | 22-12-11 | D00433B | B03 | | | TB0105G | 23 | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 13

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 208Z | | | | IH | 0-0 | 22-12-11 | D00433B | DED | | | | GDY0005 | S.. | 2 | ALL |
| 209B | 24 | PW | II | | 3-3 | 31-31-12 | D05603P | 39 | | | | TB0105F | C129 | 2 | ALL |
| 209R | 24 | PW | II | | 0-0 | 31-31-12 | D05603P | 38 | | | | TB0105F | A129 | 2 | ALL |
| 209Z | | | | II | 0-0 | 31-31-12 | D05603P | 40 | | | | GDY0006 | S.. | 2 | ALL |
| 211B | 22 | PB | IK | | 3-1 | 22-12-11 | D00433B | D11 | | | | D04379P | 10 | | ALL |
| 211R | 22 | PB | IK | | 0-0 | 22-12-11 | D00433B | E11 | | | | D04379P | 9 | | ALL |
| 212B | 24 | PW | IL | | 4-3 | 22-12-11 | D00433B | C02 | | | | D04417P | 8 | | ALL |
| 212R | 24 | PW | IL | | 0-0 | 22-12-11 | D00433B | C01 | | | | D04417P | 7 | | ALL |
| 212Z | | | | IL | 0-0 | 22-12-11 | D00433B | DED | | | | D04417P | 9 | | ALL |
| 213B | 24 | PW | IM | | 3-7 | 22-12-11 | D00433A | D09 | | | | TB0105G | 28 | 2 | ALL |
| 213R | 24 | PW | IM | | 0-0 | 22-12-11 | D00433A | C09 | | | | TB0105G | 27 | 2 | ALL |
| 213Z | | | | IM | 0-0 | 22-12-11 | D00433A | DED | | | | GDY0005 | S.. | 2 | 050-099, 277-299 |
| 213Z | | | | IM | 0-0 | 22-12-11 | D00433A | DED | | | | GDY0006 | S.. | 2 | 150-199, 275-276 |
| 214B | 24 | PW | IN | | 4-0 | 22-12-11 | D04591P | 5 | | | | TB0105G | 24 | 2 | ALL |
| 214R | 24 | PW | IN | | 0-0 | 22-12-11 | D04591P | 4 | | | | TB0105G | 23 | 2 | ALL |
| 214Z | | | | IN | 0-0 | 22-12-11 | D04591P | 6 | | | | GDY0005 | S.. | 2 | ALL |
| 215B | 24 | PW | IO | | 3-0 | 22-12-11 | D05605J | 2 | | | | TB0105G | 40 | 2 | ALL |
| 215R | 24 | PW | IO | | 0-0 | 22-12-11 | D05605J | 3 | | | | TB0105G | 41 | 2 | ALL |
| 215Z | | | | IO | 0-0 | 22-12-11 | D05605J | 4 | | | | GDY0008 | S.. | 2 | ALL |
| 216B | 24 | PW | IP | | 4-0 | 22-12-11 | D00433B | B02 | | | | TB0105G | 40 | 2 | ALL |
| 216R | 24 | PW | IP | | 0-0 | 22-12-11 | D00433B | B01 | | | | TB0105G | 41 | 2 | ALL |
| 216Z | | | | IP | 0-0 | 22-12-11 | D00433B | DED | | | | GDY0008 | S.. | 2 | ALL |
| 217B | 24 | PW | IQ | | 3-6 | 22-12-31 | D05605J | 6 | | | | TB0105H | 17 | 2 | ALL |
| 217R | 24 | PW | IQ | | 0-0 | 22-12-31 | D05605J | 5 | | | | TB0105H | 15 | 2 | ALL |
| 217Z | | | | IQ | 0-0 | 22-12-31 | D05605J | 7 | | | | GDY0002 | S.. | 2 | ALL |
| 218B | 24 | PW | IR | | 3-8 | 22-12-11 | D00433A | B10 | | | | TB0105H | 17 | 2 | ALL |
| 218R | 24 | PW | IR | | 0-0 | 22-12-11 | D00433A | A10 | | | | TB0105H | 15 | 2 | ALL |
| 218Z | | | | IR | 0-0 | 22-12-11 | D00433A | DED | | | | GDY0002 | S.. | 2 | ALL |
| 219B | 24 | PW | IS | | 3-9 | 22-12-11 | D05603P | 2 | | | | TB0105G | 40 | 2 | ALL |
| 219R | 24 | PW | IS | | 0-0 | 22-12-11 | D05603P | 1 | | | | TB0105G | 41 | 2 | ALL |
| 219Z | | | | IS | 0-0 | 22-12-11 | D05603P | 3 | | | | GDY0008 | S.. | 2 | ALL |
| 220B | 24 | PW | IT | | 2-9 | 22-12-31 | D05605J | 9 | | | | TB0105G | 28 | 2 | ALL |
| 220R | 24 | PW | IT | | 0-0 | 22-12-31 | D05605J | 8 | | | | TB0105G | 27 | 2 | ALL |
| 220Z | | | | IT | 0-0 | 22-12-31 | D05605J | 10 | | | | GDY0005 | S.. | 2 | 050-099, 277-299 |
| 220Z | | | | IT | 0-0 | 22-12-31 | D05605J | 10 | | | | GDY0006 | S.. | 2 | 150-199, 275-276 |
| 221B | 24 | PW | IU | | 4-11 | 22-13-11 | D04591P | 8 | | | | TB0105H | 69 | 2 | ALL |
| 221R | 24 | PW | IU | | 0-0 | 22-13-11 | D04591P | 7 | | | | TB0105H | 67 | 2 | ALL |
| 221Z | | | | IU | 0-0 | 22-13-11 | D04591P | 9 | | | | GDY0011 | S.. | 2 | ALL |
| 222B | 24 | PW | IV | | 3-6 | 22-13-11 | D05605J | 12 | | | | TB0105H | 69 | 2 | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 14

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 222R | 24 | PW | IV | | 0-0 | 22-13-11 | D05605J | | 11 | | TB0105H | 67 | 2 | | ALL |
| 222Z | | | IV | | 0-0 | 22-13-11 | D05605J | | 13 | | GDY0011 | S.. | 2 | | ALL |
| 223B | 24 | PW | IW | | 4-6 | 22-13-11 | D00433A | | B09 | | TB0105H | 69 | 2 | | ALL |
| 223R | 24 | PW | IW | | 0-0 | 22-13-11 | D00433A | | A09 | | TB0105H | 67 | 2 | | ALL |
| 223Z | | | IW | | 0-0 | 22-13-11 | D00433A | | DED | | GDY0011 | S.. | 2 | | ALL |
| 224 | 20 | UA | | | 1-6 | 22-13-11 | D00429B | | | FM | GDY0007 | S.. | 2 | | ALL |
| 224B | 24 | PW | IX | | 4-3 | 22-13-11 | D00429B | | C07 | | D00433B | A02 | | | ALL |
| 224R | 24 | PW | IX | | 0-0 | 22-13-11 | D00429B | | B07 | | D00433B | A01 | | | ALL |
| 224Z | | | IX | | 0-0 | 22-13-11 | D00429B | | | FM | D00433B | DED | | | ALL |
| 225 | 20 | UA | | | 1-6 | 22-13-11 | D00433B | | | FN | GDY0003 | S.. | 2 | | ALL |
| 225B | 24 | PW | IY | | 4-1 | 22-13-11 | D04831P | | 11 | | D00433B | E02 | | | ALL |
| 225R | 24 | PW | IY | | 0-0 | 22-13-11 | D04831P | | 10 | | D00433B | E01 | | | ALL |
| 225Z | | | IY | | 0-0 | 22-13-11 | D04831P | | 12 | | D00433B | | | FN | ALL |
| 226B | 22 | PB | JA | | 3-10 | 22-13-11 | D04383P | | 4 | | D00433B | E06 | | | ALL |
| 226R | 22 | PB | JA | | 0-0 | 22-13-11 | D04383P | | 3 | | D00433B | F06 | | | ALL |
| 227B | 22 | PB | JB | | 3-1 | 22-13-11 | D04379P | | 18 | | D00433B | E07 | | | ALL |
| 227R | 22 | PB | JB | | 0-0 | 22-13-11 | D04379P | | 17 | | D00433B | F07 | | | ALL |
| 229 | 20 | UA | | | 1-6 | 31-31-14 | D00433B | | | FO | GDY0003 | S.. | 2 | | ALL |
| 229B | 24 | PW | JD | | 4-10 | 31-31-14 | D00433B | | D02 | | D04855P | 5 | | | ALL |
| 229R | 24 | PW | JD | | 0-0 | 31-31-14 | D00433B | | D01 | | D04855P | 4 | | | ALL |
| 229Z | | | JD | | 0-0 | 31-31-14 | D00433B | | | FO | D04855P | 6 | | | ALL |
| 230 | 20 | UA | | | 1-6 | 22-15-11 | D00433B | | | FP | GDY0003 | S.. | 2 | | ALL |
| 230B | 24 | PW | JE | | 3-2 | 22-15-11 | D05605J | | 19 | | D00433B | F02 | | | ALL |
| 230R | 24 | PW | JE | | 0-0 | 22-15-11 | D05605J | | 18 | | D00433B | F01 | | | ALL |
| 230Z | | | JE | | 0-0 | 22-15-11 | D05605J | | 20 | | D00433B | | | FP | ALL |
| 231B | 24 | PW | JF | | 3-6 | 22-15-11 | D00433A | | E01 | | TB0105G | 115 | 2 | | ALL |
| 231R | 24 | PW | JF | | 0-0 | 22-15-11 | D00433A | | D01 | | TB0105G | 114 | 2 | | ALL |
| 231Z | | | JF | | 0-0 | 22-15-11 | D00433A | | DED | | GDY0002 | S.. | 2 | | ALL |
| 232 | 20 | UA | | | 1-6 | 22-15-11 | D00433B | | | FR | GDY0004 | S.. | 2 | | ALL |
| 232B | 24 | PW | JG | | 4-10 | 22-15-11 | D00433B | | F03 | | D04855P | 23 | | | ALL |
| 232R | 24 | PW | JG | | 0-0 | 22-15-11 | D00433B | | E03 | | D04855P | 22 | | | ALL |
| 232Z | | | JG | | 0-0 | 22-15-11 | D00433B | | | FR | D04855P | 24 | | | ALL |
| 233B | 24 | PW | JH | | 3-7 | 22-15-11 | D00433A | | H03 | | TB0105G | 132 | 2 | | ALL |
| 233R | 24 | PW | JH | | 0-0 | 22-15-11 | D00433A | | G03 | | TB0105G | 133 | 2 | | ALL |
| 233Z | | | JH | | 0-0 | 22-15-11 | D00433A | | DED | | GDY0006 | S.. | 2 | | ALL |
| 235B | 24 | PL | JJ | | 6-7 | 27-32-11 | D05383P | | 11 | | TB0105F | C003 | 2 | | ALL |
| 235R | 24 | PL | JJ | | 0-0 | 27-32-11 | D05383P | | 8 | | TB0105F | A003 | 2 | | ALL |
| 236B | 24 | PW | JK | | 3-5 | 22-22-11 | D04351P | | 6 | | TB0105G | 24 | 2 | | ALL |
| 236R | 24 | PW | JK | | 0-0 | 22-22-11 | D04351P | | 5 | | TB0105G | 23 | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0100
Page 15
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | | |
| 236Z | | | JK | 0-0 | 22-22-11 | D04351P | | 17 | | | | | GDY0005 | S.. | 2 | ALL |
| 237 | 20 | UA | | 1-6 | 22-41-11 | D00433B | | | | | | | GDY0004 | S.. | 2 | ALL |
| 237B | 24 | PW | JL | 3-1 | 22-41-11 | D00433B | | C04 | | | | | D05603P | 6 | | ALL |
| 237R | 24 | PW | JL | 0-0 | 22-41-11 | D00433B | | C03 | | | | | D05603P | 5 | | ALL |
| 237Z | | | JL | 0-0 | 22-41-11 | D00433B | | | | | | | D05603P | 7 | | ALL |
| 238B | 24 | PW | JM | 6-1 | 22-41-12 | D00433A | | A02 | | | | | TB0105G | 84 | 2 | ALL |
| 238R | 24 | PW | JM | 0-0 | 22-41-12 | D00433A | | A01 | | | | | TB0105G | 83 | 2 | ALL |
| 238Z | | | JM | 0-0 | 22-41-12 | D00433A | | DED | | | | | GDY0016 | S.. | 2 | ALL |
| 239B | 24 | PW | JN | 5-4 | 22-41-12 | D05603P | | 14 | | | | | TB0105G | 84 | 2 | ALL |
| 239R | 24 | PW | JN | 0-0 | 22-41-12 | D05603P | | 13 | | | | | TB0105G | 83 | 2 | ALL |
| 239Z | | | JN | 0-0 | 22-41-12 | D05603P | | 15 | | | | | GDY0016 | S.. | 2 | ALL |
| 240B | 24 | PW | JO | 6-0 | 34-12-61 | D03691P | | 16 | | | | | TB0105G | 157 | 2 | ALL |
| 240R | 24 | PW | JO | 0-0 | 34-12-61 | D03691P | | 17 | | | | | TB0105G | 156 | 2 | ALL |
| 240Z | | | JO | 0-0 | 34-12-61 | D03691P | | 18 | | | | | GDY0009 | S.. | 2 | ALL |
| 241B | 24 | PW | JP | 3-8 | 34-61-14 | D04781P | | 22 | | | | | TB0105H | 69 | 2 | ALL |
| 241R | 24 | PW | JP | 0-0 | 34-61-14 | D04781P | | 21 | | | | | TB0105H | 67 | 2 | ALL |
| 241Z | | | JP | 0-0 | 34-61-14 | D04781P | | 23 | | | | | GDY0011 | S.. | 2 | ALL |
| 242B | 24 | PW | JQ | 2-9 | 34-61-15 | D04781P | | 10 | | | | | TB0105G | 28 | 2 | ALL |
| 242R | 24 | PW | JQ | 0-0 | 34-61-15 | D04781P | | 9 | | | | | TB0105G | 27 | 2 | ALL |
| 242Z | | | JQ | 0-0 | 34-61-15 | D04781P | | 11 | | | | | GDY0005 | S.. | 2 | 050-099, 277-299 |
| 242Z | | | JQ | 0-0 | 34-61-15 | D04781P | | 11 | | | | | GDY0006 | S.. | 2 | 150-199, 275-276 |
| 246B | 24 | PW | JU | 3-11 | 22-33-11 | D00427B | | B10 | | | | | TB0105F | C075 | 2 | ALL |
| 246R | 24 | PW | JU | 0-0 | 22-33-11 | D00427B | | B09 | | | | | TB0105F | A075 | 2 | ALL |
| 246Z | | | JU | 0-0 | 22-33-11 | D00427B | | DED | | | | | GDY0011 | S.. | 2 | 050-099, 280-299 |
| 246Z | | | JU | 0-0 | 22-33-11 | D00427B | | DED | | | | | GDY0012 | S.. | 2 | 150-199, 275-278 |
| 248B | 24 | PL | JW | 3-1 | 22-12-11 | D04351P | | 10 | | | | | D00433B | F13 | | ALL |
| 248R | 24 | PL | JW | 0-0 | 22-12-11 | D04351P | | 9 | | | | | D00433B | E13 | | ALL |
| 250B | 24 | PW | JY | 3-3 | 34-22-38 | D05655J | | 11 | | | | | TB0105G | 61 | 2 | ALL |
| 250R | 24 | PW | JY | 0-0 | 34-22-38 | D05655J | | 10 | | | | | TB0105G | 60 | 2 | ALL |
| 250Z | | | JY | 0-0 | 34-22-38 | D05655J | | 12 | | | | | GDY0010 | S.. | 2 | ALL |
| 251B | 24 | PL | KA | 3-5 | 23-51-13 | D00429B | | B01 | | | | | D04781P | 25 | | ALL |
| 251R | 24 | PL | KA | 0-0 | 23-51-13 | D00429B | | A01 | | | | | D04781P | 24 | | ALL |
| 252B | 24 | PW | KB | 3-6 | 34-31-11 | D00429B | | C11 | | | | | TB0105Z | 166 | BJ | ALL |
| 252R | 24 | PW | KB | 0-0 | 34-31-11 | D00429B | | B11 | | | | | TB0105Z | 165 | BJ | ALL |
| 252Z | | | KB | 0-0 | 34-31-11 | D00429B | | DED | | | | | GDY0010 | S.. | 2 | 050-099, 153-199, 275-299 |
| 252Z | | | KB | 0-0 | 34-31-11 | D00429B | | DED | | | | | GDY0011 | S.. | 2 | 150-152 |
| 253B | 24 | PW | KC | 4-3 | 34-22-19 | D05603P | | 30 | | | | | TB0105Z | 166 | BJ | ALL |
| 253R | 24 | PW | KC | 0-0 | 34-22-19 | D05603P | | 29 | | | | | TB0105Z | 165 | BJ | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 16

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 253Z | | | | KC | 0-0 | 34-22-19 | D05603P | | 31 | | GDY0010 | S.. | 2 | | 050-099, 153-199, 275-299 |
| 253Z | | | | KC | 0-0 | 34-22-19 | D05603P | | 31 | | GDY0011 | S.. | 2 | | 150-152 |
| 254B | 22 | PB | | KD | 4-10 | 34-31-11 | D00429B | | C15 | | D04365P | | 8 | | ALL |
| 254R | 22 | PB | | KD | 0-0 | 34-31-11 | D00429B | | B15 | | D04365P | | 9 | | ALL |
| 255B | 24 | PW | | KE | 3-6 | 34-31-11 | D00429B | | C13 | | TB0105G | | 63 | 2 | ALL |
| 255R | 24 | PW | | KE | 0-0 | 34-31-11 | D00429B | | B13 | | TB0105G | | 62 | 2 | ALL |
| 255Z | | | | KE | 0-0 | 34-31-11 | D00429B | | DED | | GDY0010 | | S.. | 2 | ALL |
| 256B | 24 | PW | | KF | 5-1 | 34-31-11 | D04365P | | 13 | | TB0105G | | 63 | 2 | ALL |
| 256R | 24 | PW | | KF | 0-0 | 34-31-11 | D04365P | | 14 | | TB0105G | | 62 | 2 | ALL |
| 256Z | | | | KF | 0-0 | 34-31-11 | D04365P | | 12 | | GDY0010 | | S.. | 2 | ALL |
| 257B | 24 | PW | | KG | 3-8 | 34-31-11 | D04781P | | 3 | | TB0105G | | 63 | 2 | ALL |
| 257R | 24 | PW | | KG | 0-0 | 34-31-11 | D04781P | | 4 | | TB0105G | | 62 | 2 | ALL |
| 257Z | | | | KG | 0-0 | 34-31-11 | D04781P | | 5 | | GDY0010 | | S.. | 2 | ALL |
| 258B | 24 | PW | | KH | 3-7 | 34-61-12 | D04781P | | 16 | | TB0105Z | | 166 | BJ | ALL |
| 258R | 24 | PW | | KH | 0-0 | 34-61-12 | D04781P | | 15 | | TB0105Z | | 165 | BJ | ALL |
| 258Z | | | | KH | 0-0 | 34-61-12 | D04781P | | 17 | | GDY0010 | | S.. | 2 | ALL |
| 259B | 24 | PW | | KI | 6-5 | 34-46-12 | D04855P | | 29 | | TB0105Z | | 166 | BJ | ALL |
| 259R | 24 | PW | | KI | 0-0 | 34-46-12 | D04855P | | 28 | | TB0105Z | | 165 | BJ | ALL |
| 259Z | | | | KI | 0-0 | 34-46-12 | D04855P | | 30 | | GDY0010 | | S.. | 2 | ALL |
| 268B | 24 | PW | | KR | 4-1 | 34-22-18 | D05653P | | 7 | | TB0105G | | 61 | 2 | ALL |
| 268R | 24 | PW | | KR | 0-0 | 34-22-18 | D05653P | | 6 | | TB0105G | | 60 | 2 | ALL |
| 268Z | | | | KR | 0-0 | 34-22-18 | D05653P | | 8 | | GDY0010 | | S.. | 2 | ALL |
| 269B | 24 | PW | | KS | 5-3 | 34-22-18 | D04417P | | 17 | | TB0105G | | 61 | 2 | ALL |
| 269R | 24 | PW | | KS | 0-0 | 34-22-18 | D04417P | | 16 | | TB0105G | | 60 | 2 | ALL |
| 269Z | | | | KS | 0-0 | 34-22-18 | D04417P | | 18 | | GDY0010 | | S.. | 2 | ALL |
| 273B | 24 | PW | | WX | 5-0 | 34-12-61 | D03691P | | 19 | | TB0105H | | 17 | 2 | ALL |
| 273R | 24 | PW | | WX | 0-0 | 34-12-61 | D03691P | | 20 | | TB0105H | | 15 | 2 | ALL |
| 273Z | | | | WX | 0-0 | 34-12-61 | D03691P | | 21 | | GDY0002 | | S.. | 2 | ALL |
| 277B | 24 | PW | | LB | 7-0 | 34-12-61 | D05259P | | 31 | | TB0105G | | 157 | 2 | ALL |
| 277R | 24 | PW | | LB | 0-0 | 34-12-61 | D05259P | | 30 | | TB0105G | | 156 | 2 | ALL |
| 277Z | | | | LB | 0-0 | 34-12-61 | D05259P | | 26 | | GDY0009 | | S.. | 2 | ALL |
| 288B | 24 | PL | | LM | 2-7 | 27-58-21 | D04367P | | 32 | | D04379P | | 44 | | ALL |
| 288R | 24 | PL | | LM | 0-0 | 27-58-21 | D04367P | | 33 | | D04379P | | 45 | | ALL |
| 289B | 24 | PW | | LN | 4-10 | 31-51-21 | D04591P | | 22 | | TB0105G | | 162 | 2 | ALL |
| 289R | 24 | PW | | LN | 0-0 | 31-51-21 | D04591P | | 21 | | TB0105G | | 161 | 2 | ALL |
| 289Z | | | | LN | 0-0 | 31-51-21 | D04591P | | 23 | | GDY0010 | | S.. | 2 | ALL |
| 290B | 24 | PW | | LO | 5-5 | 34-33-11 | D04417P | | 3 | | TB0105G | | 162 | 2 | ALL |
| 290R | 24 | PW | | LO | 0-0 | 34-33-11 | D04417P | | 2 | | TB0105G | | 161 | 2 | ALL |

WIRE LIST

D280T132

91-21-11
Section W0100
Page 17
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | | | |
| 290Z | | | LO | 0-0 | 34-33-11 | D04417P | | 1 | | | | | GDY0010 | S.. | 2 | | ALL |
| 291B | 24 | PW | LP | 3-10 | 34-22-18 | D04831P | | 20 | | | | | D05603P | 43 | | | ALL |
| 291R | 24 | PW | LP | 0-0 | 34-22-18 | D04831P | | 19 | | | | | D05603P | 42 | | | ALL |
| 291Z | | | LP | 0-0 | 34-22-18 | D04831P | | 21 | | | | | D05603P | 44 | | | ALL |
| 292B | 24 | PW | LQ | 4-3 | 34-33-11 | TB0105G | | 162 | 2 | | | | D05603P | 17 | | | ALL |
| 292R | 24 | PW | LQ | 0-0 | 34-33-11 | TB0105G | | 161 | 2 | | | | D05603P | 16 | | | ALL |
| 292Z | | | LQ | 0-0 | 34-33-11 | GDY0010 | | S.. | 2 | | | | D05603P | 18 | | | ALL |
| 293B | 22 | PB | LR | 2-7 | 27-41-11 | D04351P | | 14 | | | | | D04367P | 5 | | | ALL |
| 293R | 22 | PB | LR | 0-0 | 27-41-11 | D04351P | | 13 | | | | | D04367P | 4 | | | ALL |
| 294B | 24 | PL | LS | 4-5 | 31-31-13 | D04855P | | 9 | | | | | TB0105G | 9 | 2 | | ALL |
| 294R | 24 | PL | LS | 0-0 | 31-31-13 | D04855P | | 8 | | | | | TB0105G | 8 | 2 | | ALL |
| 295B | 24 | PW | LT | 3-3 | 34-61-12 | D04781P | | 52 | | | | | TB0105H | 51 | 2 | | ALL |
| 295R | 24 | PW | LT | 0-0 | 34-61-12 | D04781P | | 51 | | | | | TB0105H | 49 | 2 | | ALL |
| 295Z | | | LT | 0-0 | 34-61-12 | D04781P | | 53 | | | | | GDY0008 | S.. | 2 | | 050-099, 277-299 |
| 295Z | | | LT | 0-0 | 34-61-12 | D04781P | | 53 | | | | | GDY0009 | S.. | 2 | | 150-199, 275-276 |
| 296 | 20 | UA | | 2-9 | 73-21-14 | D11786A | | | | | LU | | GDY0011 | S.. | 2 | | ALL |
| 296B | 24 | PW | LU | 6-6 | 73-21-14 | D04457P | | 54 | | | | | D11786A | C12 | | | ALL |
| 296R | 24 | PW | LU | 0-0 | 73-21-14 | D04457P | | 53 | | | | | D11786A | C11 | | | ALL |
| 296Z | | | LU | 0-0 | 73-21-14 | D04457P | | 36 | | | | | D11786A | | | LU | ALL |
| 297B | 24 | PW | LV | 4-11 | 32-42-11 | D04457P | | 43 | | | | | D04831P | 35 | | | ALL |
| 297R | 24 | PW | LV | 0-0 | 32-42-11 | D04457P | | 42 | | | | | D04831P | 34 | | | ALL |
| 297Z | | | LV | 0-0 | 32-42-11 | D04457P | | 44 | | | | | D04831P | 36 | | | ALL |
| 299B | 24 | PW | LX | 3-10 | 34-22-19 | D05603P | | 27 | | | | | TB0105H | 148 | 2 | | ALL |
| 299R | 24 | PW | LX | 0-0 | 34-22-19 | D05603P | | 26 | | | | | TB0105H | 146 | 2 | | ALL |
| 299Z | | | LX | 0-0 | 34-22-19 | D05603P | | 28 | | | | | GDY0008 | S.. | 2 | | ALL |
| 302B | 22 | PC | MB | 3-1 | 22-12-11 | D00433A | | H10 | | | | | D04379P | 15 | | | ALL |
| 302R | 22 | PC | MB | 0-0 | 22-12-11 | D00433A | | J09 | | | | | D04379P | 14 | | | ALL |
| 302Y | 22 | PC | MB | 0-0 | 22-12-11 | D00433A | | H09 | | | | | D04379P | 16 | | | ALL |
| 303B | 22 | PC | MC | 3-1 | 22-12-11 | D00433B | | H10 | | | | | D04379P | 12 | | | ALL |
| 303R | 22 | PC | MC | 0-0 | 22-12-11 | D00433B | | J09 | | | | | D04379P | 11 | | | ALL |
| 303Y | 22 | PC | MC | 0-0 | 22-12-11 | D00433B | | H09 | | | | | D04379P | 13 | | | ALL |
| 305B | 22 | PC | ME | 3-10 | 22-13-11 | D04383P | | 6 | | | | | D00433B | K06 | | | ALL |
| 305R | 22 | PC | ME | 0-0 | 22-13-11 | D04383P | | 5 | | | | | D00433B | J05 | | | ALL |
| 305Y | 22 | PC | ME | 0-0 | 22-13-11 | D04383P | | 7 | | | | | D00433B | K05 | | | ALL |
| 306B | 22 | PC | MF | 3-10 | 22-13-11 | D04383P | | 9 | | | | | D00433A | K06 | | | ALL |
| 306R | 22 | PC | MF | 0-0 | 22-13-11 | D04383P | | 8 | | | | | D00433A | J05 | | | ALL |
| 306Y | 22 | PC | MF | 0-0 | 22-13-11 | D04383P | | 10 | | | | | D00433A | K05 | | | ALL |
| 307B | 22 | PC | MG | 3-1 | 22-13-11 | D04379P | | 20 | | | | | D00433B | J06 | | | ALL |
| 307R | 22 | PC | MG | 0-0 | 22-13-11 | D04379P | | 19 | | | | | D00433B | H06 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 18

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 307Y | 22 | PC | MG | | 0-0 | 22-13-11 | D04379P | | 21 | | D00433B | H05 | | | ALL |
| 308B | 22 | PC | MH | | 3-1 | 22-13-11 | D04379P | | 23 | | D00433A | J06 | | | ALL |
| 308R | 22 | PC | MH | | 0-0 | 22-13-11 | D04379P | | 22 | | D00433A | H06 | | | ALL |
| 308Y | 22 | PC | MH | | 0-0 | 22-13-11 | D04379P | | 24 | | D00433A | H05 | | | ALL |
| 312B | 24 | PX | ML | | 3-11 | 22-32-12 | D00427B | | G12 | | TB0105F | C173 | 2 | | ALL |
| 312R | 24 | PX | ML | | 0-0 | 22-32-12 | D00427B | | E09 | | TB0105F | A173 | 2 | | ALL |
| 312Y | 24 | PX | ML | | 0-0 | 22-32-12 | D00427B | | D15 | | TB0105F | A174 | 2 | | ALL |
| 312Z | | | ML | | 0-0 | 22-32-12 | D00427B | | DED | | GDY0011 | S.. | 2 | | ALL |
| 323B | 24 | PM | MW | | 2-7 | 27-58-21 | D04367P | | 29 | | D04379P | | 46 | | ALL |
| 323R | 24 | PM | MW | | 0-0 | 27-58-21 | D04367P | | 30 | | D04379P | | 47 | | ALL |
| 323Y | 24 | PM | MW | | 0-0 | 27-58-21 | D04367P | | 31 | | D04379P | | 48 | | ALL |
| 354B | 22 | PC | OD | | 6-8 | 22-32-13 | D00427A | | A11 | | D04365P | | 19 | | ALL |
| 354R | 22 | PC | OD | | 0-0 | 22-32-13 | D00427A | | A12 | | D04365P | | 18 | | ALL |
| 354Y | 22 | PC | OD | | 0-0 | 22-32-13 | D00427A | | A10 | | D04365P | | 20 | | ALL |
| 371B | 24 | PM | OU | | 2-9 | 34-12-11 | D04169P | | 19 | | TB0105G | 102 | 2 | | ALL |
| 371R | 24 | PM | OU | | 0-0 | 34-12-11 | D04169P | | 18 | | TB0105G | 101 | 2 | | ALL |
| 371Y | 24 | PM | OU | | 0-0 | 34-12-11 | D04169P | | 20 | | TB0105G | 103 | 2 | | ALL |
| 372B | 24 | PM | OV | | 3-4 | 34-12-11 | D00423B | | J02 | | D04309P | | 2 | | ALL |
| 372R | 24 | PM | OV | | 0-0 | 34-12-11 | D00423B | | H02 | | D04309P | | 1 | | ALL |
| 372Y | 24 | PM | OV | | 0-0 | 34-12-11 | D00423B | | K02 | | D04309P | | 3 | | ALL |
| 373B | 24 | PM | OW | | 3-4 | 34-12-11 | D00423B | | J04 | | D04309P | | 7 | | ALL |
| 373R | 24 | PM | OW | | 0-0 | 34-12-11 | D00423B | | H04 | | D04309P | | 6 | | ALL |
| 373Y | 24 | PM | OW | | 0-0 | 34-12-11 | D00423B | | K04 | | D04309P | | 8 | | ALL |
| 375B | 24 | PM | OY | | 2-11 | 34-12-11 | D00423B | | J11 | | TB0105G | 102 | 2 | | ALL |
| 375R | 24 | PM | OY | | 0-0 | 34-12-11 | D00423B | | H11 | | TB0105G | 101 | 2 | | ALL |
| 375Y | 24 | PM | OY | | 0-0 | 34-12-11 | D00423B | | K11 | | TB0105G | 103 | 2 | | ALL |
| 376B | 24 | PM | PA | | 2-11 | 34-12-11 | D00423B | | J10 | | TB0105G | 102 | 2 | | ALL |
| 376R | 24 | PM | PA | | 0-0 | 34-12-11 | D00423B | | H10 | | TB0105G | 101 | 2 | | ALL |
| 376Y | 24 | PM | PA | | 0-0 | 34-12-11 | D00423B | | K10 | | TB0105G | 103 | 2 | | ALL |
| 377B | 24 | PM | PB | | 2-11 | 34-12-11 | D00423B | | J12 | | TB0105F | C105 | 2 | | ALL |
| 377R | 24 | PM | PB | | 0-0 | 34-12-11 | D00423B | | H12 | | TB0105F | A105 | 2 | | ALL |
| 377Y | 24 | PM | PB | | 0-0 | 34-12-11 | D00423B | | K12 | | TB0105F | A106 | 2 | | ALL |
| 501B | 24 | PW | UA | | 2-8 | 27-11-12 | D04351P | | 21 | | TB0105H | 13 | 2 | | ALL |
| 501R | 24 | PW | UA | | 0-0 | 27-11-12 | D04351P | | 20 | | TB0105H | 11 | 2 | | ALL |
| 501Z | | | UA | | 0-0 | 27-11-12 | D04351P | | 22 | | GDY0001 | S.. | 2 | | 050-099 |
| 501Z | | | UA | | 0-0 | 27-11-12 | D04351P | | 22 | | GDY0002 | S.. | 2 | | 150-199, 275-299 |
| 502B | 20 | PR | UB | | 4-9 | 34-12-11 | D00423C | | 6 | | GDY0008 | A.. | 2 | | ALL |
| 502R | 20 | PR | UB | | 0-0 | 34-12-11 | D00423C | | 4 | | TB0105H | 143 | 2 | | ALL |
| 502Z | | | UB | | 0-0 | 34-12-11 | D00423C | | DED | | TB0105H | DED | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0100
 Page 19
 May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | | |
| 503B | 20 | PR | UC | | 4-6 | 34-12-11 | D00423C | | 11 | | | GDY0007 | A.. | 2 | | ALL |
| 503R | 20 | PR | UC | | 0-0 | 34-12-11 | D00423C | | 10 | | | TB0105H | 37 | 2 | | ALL |
| 503Z | | | UC | | 0-0 | 34-12-11 | D00423C | | DED | | | TB0105H | DED | | | ALL |
| 504B | 20 | PR | UD | | 4-6 | 34-12-11 | D00423C | | 9 | | | GDY0007 | A.. | 2 | | ALL |
| 504R | 20 | PR | UD | | 0-0 | 34-12-11 | D00423C | | 5 | | | TB0105H | 37 | 2 | | ALL |
| 504Z | | | UD | | 0-0 | 34-12-11 | D00423C | | DED | | | TB0105H | DED | | | ALL |
| 507B | 22 | PR | UG | | 4-8 | 34-12-11 | D04309P | | 5 | | | GDY0007 | A.. | 2 | | ALL |
| 507R | 22 | PR | UG | | 0-0 | 34-12-11 | D04309P | | 4 | | | TB0105H | 37 | 2 | | ALL |
| 507Z | | | UG | | 0-0 | 34-12-11 | D04309P | | DED | | | TB0105H | DED | | | ALL |
| 508B | 22 | PR | UH | | 2-11 | 34-12-11 | D04169P | | 13 | | | D00423B | J08 | | | ALL |
| 508R | 22 | PR | UH | | 0-0 | 34-12-11 | D04169P | | 12 | | | D00423B | H08 | | | ALL |
| 508Z | | | UH | | 0-0 | 34-12-11 | D04169P | | 14 | | | D00423B | K08 | | | ALL |
| 510B | 24 | PW | UJ | | 3-2 | 34-12-12 | D00423B | | B02 | | | TB0105H | 13 | 2 | | ALL |
| 510R | 24 | PW | UJ | | 0-0 | 34-12-12 | D00423B | | A02 | | | TB0105H | 11 | 2 | | ALL |
| 510Z | | | UJ | | 0-0 | 34-12-12 | D00423B | | DED | | | GDY0001 | S.. | 2 | | 050-099 |
| 510Z | | | UJ | | 0-0 | 34-12-12 | D00423B | | DED | | | GDY0002 | S.. | 2 | | 150-199, 275-299 |
| 511B | 24 | PW | UK | | 3-0 | 34-12-12 | D00423B | | B08 | | | TB0105H | 6 | 2 | | ALL |
| 511R | 24 | PW | UK | | 0-0 | 34-12-12 | D00423B | | A08 | | | TB0105H | 4 | 2 | | ALL |
| 511Z | | | UK | | 0-0 | 34-12-12 | D00423B | | DED | | | GDY0001 | S.. | 2 | | ALL |
| 512B | 24 | PW | UL | | 3-7 | 34-12-12 | D04781P | | 7 | | | TB0105H | 6 | 2 | | ALL |
| 512R | 24 | PW | UL | | 0-0 | 34-12-12 | D04781P | | 6 | | | TB0105H | 4 | 2 | | ALL |
| 512Z | | | UL | | 0-0 | 34-12-12 | D04781P | | 8 | | | GDY0001 | S.. | 2 | | ALL |
| 513B | 24 | PW | UM | | 4-7 | 34-12-12 | TB0105H | | 148 | 2 | | D00423B | B04 | | | ALL |
| 513R | 24 | PW | UM | | 0-0 | 34-12-12 | TB0105H | | 146 | 2 | | D00423B | A04 | | | ALL |
| 513Z | | | UM | | 0-0 | 34-12-12 | GDY0008 | | S.. | 2 | | D00423B | DED | | | ALL |
| 514B | 24 | PW | UN | | 4-1 | 34-21-11 | D04831P | | 17 | | | TB0105H | 148 | 2 | | ALL |
| 514R | 24 | PW | UN | | 0-0 | 34-21-11 | D04831P | | 16 | | | TB0105H | 146 | 2 | | ALL |
| 514Z | | | UN | | 0-0 | 34-21-11 | D04831P | | 18 | | | GDY0008 | S.. | 2 | | ALL |
| 515B | 24 | PW | UO | | 4-5 | 34-46-12 | D04855P | | 26 | | | TB0105H | 6 | 2 | | ALL |
| 515R | 24 | PW | UO | | 0-0 | 34-46-12 | D04855P | | 25 | | | TB0105H | 4 | 2 | | ALL |
| 515Z | | | UO | | 0-0 | 34-46-12 | D04855P | | 27 | | | GDY0001 | S.. | 2 | | ALL |
| 517B | 24 | PW | UQ | | 2-8 | 21-31-11 | D05603P | | 51 | | | TB0105H | 6 | 2 | | ALL |
| 517R | 24 | PW | UQ | | 0-0 | 21-31-11 | D05603P | | 50 | | | TB0105H | 4 | 2 | | ALL |
| 517Z | | | UQ | | 0-0 | 21-31-11 | D05603P | | 52 | | | GDY0001 | S.. | 2 | | ALL |
| 518B | 24 | PW | UR | | 4-3 | 34-12-61 | D00423B | | B06 | | | TB0105F | C036 | 2 | | ALL |
| 518R | 24 | PW | UR | | 0-0 | 34-12-61 | D00423B | | A06 | | | TB0105F | A036 | 2 | | ALL |
| 518Z | | | UR | | 0-0 | 34-12-61 | D00423B | | DED | | | GDY0007 | S.. | 2 | | 050-099, 277-299 |
| 518Z | | | UR | | 0-0 | 34-12-61 | D00423B | | DED | | | GDY0006 | S.. | 2 | | 150-199, 275-276 |
| 520B | 24 | PW | UT | | 4-6 | 34-12-61 | TB0105H | | 51 | 2 | | TB0105H | 6 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 20

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 520R | 24 | PW | UT | | 0-0 | 34-12-61 | TB0105H | 49 | 2 | | TB0105H | 4 | 2 | | ALL |
| 520Z | | | UT | | 0-0 | 34-12-61 | TB0105H | DED | | | GDY0001 | S.. | 2 | | ALL |
| 523B | 24 | PW | UW | | 4-5 | 27-51-51 | D04855P | 36 | | | TB0105H | 6 | 2 | | ALL |
| 523R | 24 | PW | UW | | 0-0 | 27-51-51 | D04855P | 35 | | | TB0105H | 4 | 2 | | ALL |
| 523Z | | | UW | | 0-0 | 27-51-51 | D04855P | 37 | | | GDY0001 | S.. | 2 | | ALL |
| 524B | 24 | PL | UX | | 2-4 | 23-51-13 | D04781P | 2 | | | D05605J | 28 | | | ALL |
| 524R | 24 | PL | UX | | 0-0 | 23-51-13 | D04781P | 1 | | | D05605J | 27 | | | ALL |
| 525B | 24 | PW | UY | | 3-3 | 34-12-61 | TB0105H | 17 | 2 | | TB0105H | 13 | 2 | | ALL |
| 525R | 24 | PW | UY | | 0-0 | 34-12-61 | TB0105H | 15 | 2 | | TB0105H | 11 | 2 | | ALL |
| 525Z | | | UY | | 0-0 | 34-12-61 | TB0105H | DED | | | GDY0001 | S.. | 2 | | 050-099 |
| 527 | 20 | UA | | | 1-6 | 34-45-14 | GDX0009 | S.. | 2 | | GDY0002 | S.. | 2 | | 150-199, 275-299 |
| 527B | 24 | PW | VB | | 5-2 | 34-45-14 | D06141P | 2 | | | D02463E | REF | | VB | ALL |
| 527R | 24 | PW | VB | | 0-0 | 34-45-14 | D06141P | 1 | | | D02463E | B07 | | | ALL |
| 527Z | | | VB | | 0-0 | 34-45-14 | D06141P | 3 | | | D02463E | A07 | | | ALL |
| 529B | 24 | PW | VD | | 3-6 | 34-22-39 | D05655J | 8 | | | REF | | | VB | ALL |
| 529R | 24 | PW | VD | | 0-0 | 34-22-39 | D05655J | 7 | | | TB0105H | 148 | 2 | | ALL |
| 529Z | | | VD | | 0-0 | 34-22-39 | D05655J | 9 | | | TB0105H | 146 | 2 | | ALL |
| 530B | 24 | PW | VE | | 2-10 | 34-13-21 | D04169P | 26 | | | GDY0008 | S.. | 2 | | ALL |
| 530R | 24 | PW | VE | | 0-0 | 34-13-21 | D04169P | 25 | | | TB0105H | 6 | 2 | | ALL |
| 530Z | | | VE | | 0-0 | 34-13-21 | D04169P | 27 | | | TB0105H | 4 | 2 | | ALL |
| 531B | 24 | PW | VF | | 3-11 | 22-33-11 | D00427A | B06 | | | GDY0001 | S.. | 2 | | ALL |
| 531R | 24 | PW | VF | | 0-0 | 22-33-11 | D00427A | B05 | | | TB0105F | C076 | 2 | | ALL |
| 531Z | | | VF | | 0-0 | 22-33-11 | D00427A | DED | | | TB0105F | A076 | 2 | | ALL |
| 533B | 24 | PW | VH | | 2-10 | 27-32-11 | D04323P | 14 | | | GDY0012 | S.. | 2 | | ALL |
| 533R | 24 | PW | VH | | 0-0 | 27-32-11 | D04323P | 13 | | | TB0105G | 28 | 2 | | ALL |
| 533Z | | | VH | | 0-0 | 27-32-11 | D04323P | 15 | | | TB0105G | 27 | 2 | | ALL |
| 534B | 24 | PW | VI | | 3-11 | 22-32-12 | D00427A | C05 | | | GDY0005 | S.. | 2 | | ALL |
| 534R | 24 | PW | VI | | 0-0 | 22-32-12 | D00427A | C04 | | | TB0105H | 170 | 2 | | ALL |
| 534Z | | | VI | | 0-0 | 22-32-12 | D00427A | DED | | | TB0105H | 168 | 2 | | ALL |
| 535 | 24 | PK | | | 6-11 | 22-32-13 | TB0105G | 96 | 2 | | GDY0011 | S.. | 2 | | ALL |
| 536B | 24 | PW | VK | | 6-1 | 73-21-14 | D04457P | 46 | | | D04457P | 22 | | | ALL |
| 536R | 24 | PW | VK | | 0-0 | 73-21-14 | D04457P | 45 | | | TB0105H | 170 | 2 | | ALL |
| 536Z | | | VK | | 0-0 | 73-21-14 | D04457P | 47 | | | TB0105H | 168 | 2 | | ALL |
| 537B | 24 | PW | VL | | 3-9 | 77-35-11 | D11786A | D02 | | | GDY0011 | S.. | 2 | | ALL |
| 537R | 24 | PW | VL | | 0-0 | 77-35-11 | D11786A | D01 | | | TB0105G | 196 | 2 | | ALL |
| 537Z | | | VL | | 0-0 | 77-35-11 | D11786A | DED | | | TB0105G | 197 | 2 | | ALL |
| 538B | 24 | PW | VM | | 5-4 | 77-35-11 | D05653P | 2 | | | GDY0016 | S.. | 2 | | ALL |
| 538R | 24 | PW | VM | | 0-0 | 77-35-11 | D05653P | 1 | | | TB0105G | 196 | 2 | | ALL |
| | | | | | | | | | | | TB0105G | 197 | 2 | | ALL |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|-------|--------|---------|------|------|--------|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 538Z | | | VM | 0-0 | 77-35-11 | D05653P | | | 3 | | GDY0016 | S.. | 2 | | ALL |
| 539B | 24 | PW | VN | 5-4 | 77-35-11 | D05653P | | | 11 | | TB0105G | 194 | 2 | | ALL |
| 539R | 24 | PW | VN | 0-0 | 77-35-11 | D05653P | | | 10 | | TB0105G | 195 | 2 | | ALL |
| 539Z | | | VN | 0-0 | 77-35-11 | D05653P | | | 12 | | GDY0016 | S.. | 2 | | ALL |
| 540B | 24 | PW | VO | 3-9 | 77-35-11 | D11786B | | D02 | | | TB0105G | 194 | 2 | | ALL |
| 540R | 24 | PW | VO | 0-0 | 77-35-11 | D11786B | | D01 | | | TB0105G | 195 | 2 | | ALL |
| 540Z | | | VO | 0-0 | 77-35-11 | D11786B | | DED | | | GDY0016 | S.. | 2 | | ALL |
| 541B | 24 | PW | VP | 6-5 | 22-32-12 | D05259P | | | 16 | | TB0105H | 170 | 2 | | ALL |
| 541R | 24 | PW | VP | 0-0 | 22-32-12 | D05259P | | | 15 | | TB0105H | 168 | 2 | | ALL |
| 541Z | | | VP | 0-0 | 22-32-12 | D05259P | | | 17 | | GDY0011 | S.. | 2 | | ALL |
| 544 | 20 | UA | | 1-6 | 34-45-12 | GDX0009 | | | S.. 2 | | D02463E | REF | | VS | ALL |
| 544B | 24 | PW | VS | 4-1 | 34-45-12 | D04781P | | | 48 | | D02463E | K15 | | | ALL |
| 544R | 24 | PW | VS | 0-0 | 34-45-12 | D04781P | | | 47 | | D02463E | J15 | | | ALL |
| 544Z | | | VS | 0-0 | 34-45-12 | D04781P | | | 46 | | D02463E | REF | | VS | ALL |
| 546 | 20 | UA | | 1-6 | 34-45-14 | GDX0010 | | | S.. 2 | | TB0105G | REF | | VU | 050-099, 150-156, 162-166, 275-276 |
| 546 | 20 | UA | | 1-6 | 34-45-14 | GDX0010 | | | S.. 2 | | TB0105Y | REF | | VU | 157, 167-199, 277-299 |
| 546B | 24 | PW | VU | 3-4 | 34-45-14 | TB0105G | | | 74 2 | | D02463E | D07 | | | 050-099, 150-156, 162-166, 275-276 |
| 546B | 24 | PW | VU | 3-4 | 34-45-14 | TB0105Y | | C073 | BJ | | D02463E | D07 | | | 157, 167-199, 277-299 |
| 546R | 24 | PW | VU | 0-0 | 34-45-14 | TB0105G | | | 73 2 | | D02463E | C07 | | | 050-099, 150-156, 162-166, 275-276 |
| 546R | 24 | PW | VU | 0-0 | 34-45-14 | TB0105Y | | A073 | BJ | | D02463E | C07 | | | 157, 167-199, 277-299 |
| 546Z | | | VU | 0-0 | 34-45-14 | D02463E | | | DED | | TB0105G | REF | | VU | 050-099, 150-156, 162-166, 275-276 |
| 546Z | | | VU | 0-0 | 34-45-14 | D02463E | | | DED | | TB0105Y | REF | | VU | 157, 167-199, 277-299 |
| 549 | 20 | UA | | 1-6 | 34-45-12 | GDX0009 | | | S.. 2 | | D02463E | REF | | VX | 050-099, 150-154, 275-299 |
| 549 | 20 | UA | | 2-11 | 34-45-12 | GDX0009 | | | S.. 2 | | D02463E | REF | | VX | 153-159 |
| 549B | 24 | PW | VX | 6-8 | 34-45-12 | D05827P | | | 2 | | D02463E | G14 | | | 050-099, 150-152, 155-199, 275-299 |
| 549B | 24 | PW | VX | 4-1 | 34-45-12 | D04781P | | | 40 | | D02463E | G14 | | | 153-154 |
| 549R | 24 | PW | VX | 0-0 | 34-45-12 | D05827P | | | 1 | | D02463E | F14 | | | 050-099, 150-152, 155-199, 275-299 |
| 549R | 24 | PW | VX | 0-0 | 34-45-12 | D04781P | | | 39 | | D02463E | F14 | | | 153-154 |
| 549Z | | | VX | 0-0 | 34-45-12 | D05827P | | | 3 | | D02463E | REF | | VX | 050-099, 150-152, 155-199, 275-299 |
| 549Z | | | VX | 0-0 | 34-45-12 | D04781P | | | 38 | | D02463E | REF | | VX | 153-154 |
| 551 | 20 | UA | | 2-9 | 73-21-14 | D11786B | | | | WA | GDX0011 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 22

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 551B | 24 | PW | WA | | 6-6 | 73-21-14 | D04457P | | | | D11786B | B08 | | | ALL |
| 551R | 24 | PW | WA | | 0-0 | 73-21-14 | D04457P | | | | D11786B | B07 | | | ALL |
| 551Z | | | WA | | 0-0 | 73-21-14 | D04457P | | | | D11786B | | | WA | ALL |
| 552B | 24 | PW | WB | | 4-8 | 31-31-14 | D04941P | | | | TB0105G | 179 | 2 | | 050-099 |
| 552B | 22 | PR | WB | | 4-8 | 31-31-14 | D04941P | | | | TB0105G | 179 | 2 | | 150-199, 275-299 |
| 552R | 24 | PW | WB | | 0-0 | 31-31-14 | D04941P | | | | TB0105G | 178 | 2 | | 050-099 |
| 552R | 22 | PR | WB | | 0-0 | 31-31-14 | D04941P | | | | TB0105G | 178 | 2 | | 150-199, 275-299 |
| 552Z | | | WB | | 0-0 | 31-31-14 | D04941P | | | | GDY0012 | S.. | 2 | | ALL |
| 555 | 20 | UA | | | 1-6 | 34-45-12 | GDX0009 | S.. | 2 | | D02463E | REF | | WE | ALL |
| 555B | 24 | PW | WE | | 7-3 | 34-45-12 | D06143P | | | | D02463E | B14 | | | 050-099, 150-152, 155-199, 275-299 |
| 555B | 24 | PW | WE | | 6-11 | 34-45-12 | D04855P | | | | D02463E | B14 | | | 153-154 |
| 555R | 24 | PW | WE | | 0-0 | 34-45-12 | D06143P | | | | D02463E | A14 | | | 050-099, 150-152, 155-199, 275-299 |
| 555R | 24 | PW | WE | | 0-0 | 34-45-12 | D04855P | | | | D02463E | A14 | | | 153-154 |
| 555Z | | | WE | | 0-0 | 34-45-12 | D06143P | | | | D02463E | REF | | WE | 050-099, 150-152, 155-199, 275-299 |
| 555Z | | | WE | | 0-0 | 34-45-12 | D04855P | | | | D02463E | REF | | WE | 153-154 |
| 560 | 20 | UA | | | 1-6 | 34-45-12 | GDX0009 | S.. | 2 | | D02463E | REF | | WJ | ALL |
| 560B | 24 | PW | WJ | | 7-3 | 34-45-12 | D06143P | | | | D02463E | J14 | | | 050-099, 150-152, 155-199, 275-299 |
| 560B | 24 | PW | WJ | | 6-11 | 34-45-12 | D04855P | | | | D02463E | J14 | | | 153-154 |
| 560R | 24 | PW | WJ | | 0-0 | 34-45-12 | D06143P | | | | D02463E | H14 | | | 050-099, 150-152, 155-199, 275-299 |
| 560R | 24 | PW | WJ | | 0-0 | 34-45-12 | D04855P | | | | D02463E | H14 | | | 153-154 |
| 560Z | | | WJ | | 0-0 | 34-45-12 | D06143P | | | | D02463E | REF | | WJ | 050-099, 150-152, 155-199, 275-299 |
| 560Z | | | WJ | | 0-0 | 34-45-12 | D04855P | | | | D02463E | REF | | WJ | 153-154 |
| 564 | 20 | UA | | | 1-6 | 34-45-14 | GDX0009 | S.. | 2 | | D02463F | REF | | WN | ALL |
| 564B | 24 | PW | WN | | 6-8 | 34-45-14 | D05827P | | | | D02463F | E03 | | | 050-099, 150-152, 155-199, 275-299 |
| 564B | 24 | PW | WN | | 4-1 | 34-45-14 | D04781P | | | | D02463F | E03 | | | 153-154 |
| 564R | 24 | PW | WN | | 0-0 | 34-45-14 | D05827P | | | | D02463F | D03 | | | 050-099, 150-152, 155-199, 275-299 |
| 564R | 24 | PW | WN | | 0-0 | 34-45-14 | D04781P | | | | D02463F | D03 | | | 153-154 |
| 564Z | | | WN | | 0-0 | 34-45-14 | D05827P | | | | D02463F | REF | | WN | 050-099, 150-152, 155-199, 275-299 |
| 564Z | | | WN | | 0-0 | 34-45-14 | D04781P | | | | D02463F | REF | | WN | 153-154 |
| 568 | 20 | UA | | | 1-6 | 34-45-14 | GDX0009 | S.. | 2 | | TB0105G | REF | | WR | ALL |

WIRE LIST
D280T132

91-21-11
Section W0100
Page 23
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 568B | 24 | PW | WR | | 3-5 | 34-45-14 | TB0105G | 162 | 2 | | D02463E | J13 | | | ALL |
| 568R | 24 | PW | WR | | 0-0 | 34-45-14 | TB0105G | 161 | 2 | | D02463E | H13 | | | ALL |
| 568Z | | | WR | | 0-0 | 34-45-14 | D02463E | DED | | | TB0105G | REF | | WR | ALL |
| 573B | 24 | PW | KW | | 8-0 | 31-31-20 | D05247P | 31 | | | TB0105Y | CAP | Y | | 050-099 |
| 573B | 24 | PW | KW | | 4-7 | 31-31-20 | D05247P | 31 | | | TB0105Y | C141 | % | | 150-199, 275-299 |
| 573R | 24 | PW | KW | | 0-0 | 31-31-20 | D05247P | 30 | | | TB0105Y | CAP | Y | | 050-099 |
| 573R | 24 | PW | KW | | 0-0 | 31-31-20 | D05247P | 30 | | | TB0105Y | A141 | % | | 150-199, 275-299 |
| 573Z | | | KW | | 0-0 | 31-31-20 | D05247P | 32 | | | GDY0007 | S.. | 2 | | ALL |
| 574B | 24 | PW | KX | | 5-1 | 31-31-20 | D05247P | 34 | | | TB0105Z | 166 | BJ | | ALL |
| 574R | 24 | PW | KX | | 0-0 | 31-31-20 | D05247P | 33 | | | TB0105Z | 165 | BJ | | ALL |
| 574Z | | | KX | | 0-0 | 31-31-20 | D05247P | 35 | | | GDY0010 | S.. | 2 | | ALL |
| 575B | 24 | PW | WY | | 4-8 | 31-35-12 | D04781P | 33 | | | TB0105G | 196 | 2 | | ALL |
| 575R | 24 | PW | WY | | 0-0 | 31-35-12 | D04781P | 32 | | | TB0105G | 197 | 2 | | ALL |
| 575Z | | | WY | | 0-0 | 31-35-12 | D04781P | 34 | | | GDY0016 | S.. | 2 | | ALL |
| 576B | 24 | PW | XA | | 4-8 | 31-35-12 | D04781P | 36 | | | TB0105G | 194 | 2 | | ALL |
| 576R | 24 | PW | XA | | 0-0 | 31-35-12 | D04781P | 35 | | | TB0105G | 195 | 2 | | ALL |
| 576Z | | | XA | | 0-0 | 31-35-12 | D04781P | 37 | | | GDY0016 | S.. | 2 | | ALL |
| 577B | 24 | PW | XB | | 3-3 | 31-35-12 | D04781P | 29 | | | TB0105H | 51 | 2 | | ALL |
| 577R | 24 | PW | XB | | 0-0 | 31-35-12 | D04781P | 28 | | | TB0105H | 49 | 2 | | ALL |
| 577Z | | | XB | | 0-0 | 31-35-12 | D04781P | 30 | | | GDY0008 | S.. | 2 | | ALL |
| 578B | 22 | PB | XC | | 3-0 | 31-31-25 | D04337P | 24 | | | D05247P | 23 | | | 050-099, 150-199 |
| 578R | 22 | PB | XC | | 0-0 | 31-31-25 | D04337P | 23 | | | D05247P | 22 | | | 050-099, 150-199 |
| 579B | 22 | PB | XD | | 3-0 | 31-31-25 | D04337P | 27 | | | D05247P | 26 | | | 050-099, 150-199 |
| 579R | 22 | PB | XD | | 0-0 | 31-31-25 | D04337P | 26 | | | D05247P | 25 | | | 050-099, 150-199 |
| 580B | 22 | PB | XE | | 3-0 | 31-31-25 | D04337P | 30 | | | D05247P | 28 | | | 050-099, 150-199 |
| 580R | 22 | PB | XE | | 0-0 | 31-31-25 | D04337P | 29 | | | D05247P | 27 | | | 050-099, 150-199 |
| 582B | 24 | PW | XG | | 4-4 | 77-12-11 | D04457P | 5 | | | TB0105F | C124 | 2 | | 150-157, 275-276 |
| 582R | 24 | PW | XG | | 0-0 | 77-12-11 | D04457P | 4 | | | TB0105F | A124 | 2 | | 150-157, 275-276 |
| 582Z | | | XG | | 0-0 | 77-12-11 | D04457P | 6 | | | GDY0006 | S.. | 2 | | 150-157, 275-276 |
| 583 | 20 | UA | | | 1-6 | 34-45-14 | GDX0010 | S.. | 2 | | TB0105G | REF | | XH | 050-099, 150-156, 162-166, 275-276 |
| 583 | 20 | UA | | | 1-6 | 34-45-14 | GDX0010 | S.. | 2 | | TB0105Y | REF | | XH | 157, 167-199, 277-299 |
| 583B | 24 | PW | XH | | 4-7 | 34-45-14 | D05653P | 24 | | | TB0105G | 74 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 583B | 24 | PW | XH | | 4-7 | 34-45-14 | D05653P | 24 | | | TB0105Y | C073 | BJ | | 157, 167-199, 277-299 |
| 583R | 24 | PW | XH | | 0-0 | 34-45-14 | D05653P | 23 | | | TB0105G | 73 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 583R | 24 | PW | XH | | 0-0 | 34-45-14 | D05653P | 23 | | | TB0105Y | A073 | BJ | | 157, 167-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 24

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 583Z | | | | XH | 0-0 | 34-45-14 | D05653P | | 25 | | TB0105G | REF | | XH | 050-099, 150-156, 162-166, 275-276 |
| 583Z | | | | XH | 0-0 | 34-45-14 | D05653P | | 25 | | TB0105Y | REF | | XH | 157, 167-199, 277-299 |
| 584 | 22 | PA | | | 4-9 | 34-45-13 | D04323P | | 4 | | TB0105G | 186 | 2 | | 050-099, 150-166, 275-276 |
| 585 | 20 | UA | | | 1-6 | 34-45-14 | GDX0010 | | S.. | 2 | TB0105G | REF | | XJ | 050-099, 150-156, 162-166, 275-276 |
| 585 | 20 | UA | | | 1-6 | 34-45-14 | GDX0010 | | S.. | 2 | TB0105Y | REF | | XJ | 157, 167-199, 277-299 |
| 585B | 24 | PW | XJ | | 3-9 | 34-45-14 | D05605J | | 23 | | TB0105G | 74 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 585B | 24 | PW | XJ | | 3-9 | 34-45-14 | D05605J | | 23 | | TB0105Y | C073 | BJ | | 157, 167-199, 277-299 |
| 585R | 24 | PW | XJ | | 0-0 | 34-45-14 | D05605J | | 22 | | TB0105G | 73 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 585Z | 24 | PW | XJ | | 0-0 | 34-45-14 | D05605J | | 22 | | TB0105Y | A073 | BJ | | 157, 167-199, 277-299 |
| 585Z | 24 | PW | XJ | | 0-0 | 34-45-14 | D05605J | | 24 | | TB0105G | REF | | XJ | 050-099, 150-156, 162-166, 275-276 |
| 585Z | 22 | PA | | XJ | 0-0 | 34-45-14 | D05605J | | 24 | | TB0105Y | REF | | XJ | 157, 167-199, 277-299 |
| 586 | 22 | PA | | | 4-1 | 34-45-13 | TB0105G | | 186 | 2 | D02463E | CAP | Y | | 050-099, 150-166, 275-276 |
| 588 | 20 | UA | | | 1-6 | 34-45-14 | GDX0010 | | S.. | 2 | TB0105G | REF | | XM | 050-099, 150-156, 162-166, 275-276 |
| 588 | 20 | UA | | | 1-6 | 34-45-14 | GDX0010 | | S.. | 2 | TB0105Y | REF | | XM | 157, 167-199, 277-299 |
| 588B | 24 | PW | XM | | 6-5 | 34-45-14 | D05259P | | 28 | | TB0105G | 74 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 588B | 24 | PW | XM | | 6-5 | 34-45-14 | D05259P | | 28 | | TB0105Y | C073 | BJ | | 157, 167-199, 277-299 |
| 588R | 24 | PW | XM | | 0-0 | 34-45-14 | D05259P | | 25 | | TB0105G | 73 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 588R | 24 | PW | XM | | 0-0 | 34-45-14 | D05259P | | 25 | | TB0105Y | A073 | BJ | | 157, 167-199, 277-299 |
| 588Z | 24 | PW | XM | | 0-0 | 34-45-14 | D05259P | | 29 | | TB0105G | REF | | XM | 050-099, 150-156, 162-166, 275-276 |
| 588Z | 24 | PW | XM | | 0-0 | 34-45-14 | D05259P | | 29 | | TB0105Y | REF | | XM | 157, 167-199, 277-299 |
| 589 | 22 | PA | | XM | 0-0 | 34-45-14 | D05259P | | 29 | | TB0105G | REF | | XM | 157, 167-199, 277-299 |
| 589 | 22 | PA | | | 3-7 | 34-45-14 | TB0105G | | 158 | 2 | D02463E | E13 | | | 050-099, 150-152, 155-199, 275-299 |
| 589 | 22 | PA | | | 3-7 | 34-45-14 | TB0105F | | A158 | 2 | D02463E | E13 | | | 153-154 |
| 590 | 20 | UA | | | 1-6 | 34-45-14 | TB0105Y | | REF | | GDX0011 | S.. | 2 | | 157, 167-199, 277-299 |
| 590B | 24 | PW | X0 | | 3-8 | 34-45-14 | TB0105F | | C054 | 2 | D02463E | H07 | | | 050-099, 150-156, 162-166, 275-276 |
| 590B | 24 | PW | X0 | | 3-4 | 34-45-14 | TB0105Y | | C074 | BJ | D02463E | H07 | | | 157, 167-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0100
Page 25
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|--|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | | |
| 590R | 24 | PW | X0 | 0-0 | 34-45-14 | TB0105F | A054 | 2 | | D02463E | G07 | | | 050-099, 150-156, 162-166, 275-276 | | |
| 590R | 24 | PW | XO | 0-0 | 34-45-14 | TB0105Y | A074 | BJ | | D02463E | G07 | | | 157, 167-199, 277-299 | | |
| 590Z | | | X0 | 0-0 | 34-45-14 | GDY0009 | S.. | 2 | | D02463E | DED | | | 050-099, 150-156, 162-166, 275-276 | | |
| 590Z | | | XO | 0-0 | 34-45-14 | TB0105Y | REF | | XO | D02463E | DED | | | 157, 167-199, 277-299 | | |
| 592 | 20 | UA | | 1-6 | 34-45-14 | GDX0010 | S.. | 2 | | TB0105F | REF | | XQ | 050-099, 150-156, 162-166, 275-276 | | |
| 592B | 24 | PW | XQ | 3-4 | 34-45-14 | TB0105F | C176 | 2 | | D02463E | CAP | Y | | 050-099, 150-156, 162-166, 275-276 | | |
| 592R | 24 | PW | XQ | 0-0 | 34-45-14 | TB0105F | A176 | 2 | | D02463E | CAP | Y | | 050-099, 150-156, 162-166, 275-276 | | |
| 592Z | | | XQ | 0-0 | 34-45-14 | TB0105F | REF | | XQ | D02463E | DED | | | 050-099, 150-156, 162-166, 275-276 | | |
| 593 | 22 | PA | | 4-5 | 34-45-12 | TB0105G | | 2 | | D02463E | H06 | | | ALL | | |
| 594 | 22 | PA | | 4-5 | 34-45-12 | TB0105G | | 2 | | D02463E | J06 | | | ALL | | |
| 595 | 22 | PA | | 4-5 | 34-45-12 | TB0105G | | 2 | | D02463E | K06 | | | ALL | | |
| 598 | 22 | PA | | 2-8 | 34-45-13 | GDX0011 | D.. | 2 | | D02463E | J07 | | | 153-154 | | |
| 599 | 20 | UA | | 1-6 | 34-45-14 | TB0105Y | REF | | XX | GDX0011 | S.. | 2 | | 157, 167-199, 277-299 | | |
| 599B | 24 | PW | XX | 3-9 | 34-45-14 | D05605J | | 41 | | TB0105Y | C074 | BJ | | 157, 167-199, 277-299 | | |
| 599R | 24 | PW | XX | 0-0 | 34-45-14 | D05605J | | 40 | | TB0105Y | A074 | BJ | | 157, 167-199, 277-299 | | |
| 599Z | | | XX | 0-0 | 34-45-14 | D05605J | | 42 | | TB0105Y | REF | | XX | 157, 167-199, 277-299 | | |
| 600 | 20 | PA | | 2-5 | 34-45-11 | GDX0010 | A.. | 2 | | D02463C | 7 | | | ALL | | |
| 602 | 24 | PK | | 0-7 | 22-11-12 | D00433A | B11 | | | D00433A | B12 | | | 050-099 | | |
| 603 | 20 | PA | | 2-5 | 34-45-11 | GDX0010 | D.. | 2 | | D02463C | 8 | | | ALL | | |
| 604 | 24 | PK | | 7-2 | 31-31-14 | D04855P | | 10 | | D11786B | D12 | | | ALL | | |
| 605 | 24 | PK | | 3-4 | 77-35-11 | D11786C | | 2 | | TB0105F | A077 | 2 | | ALL | | |
| 607 | 24 | PK | | 2-6 | 22-11-12 | D00433A | D04 | | | D00433B | A04 | | | 050-099 | | |
| 607 | 24 | PK | | 2-8 | 22-11-12 | D00433A | D04 | | | D00433B | A04 | | | 150-199, 275-299 | | |
| 608 | 22 | PA | | 2-9 | 77-35-11 | D11786C | | 4 | | GDX0011 | A.. | 2 | | ALL | | |
| 609 | 22 | PA | | 2-9 | 77-35-11 | D11786C | | 3 | | GDX0011 | S.. | 2 | | ALL | | |
| 610 | 16 | PQ | YJ | 2-5 | 27-32-31 | D04457P | | 51 | FL | D04379P | 53 | FL | | 050-099 | | |
| 610 | 16 | PQ | YJ | 3-5 | 27-32-31 | D04457P | | 51 | FL | D04379P | 53 | FL | | 150-199, 275-299 | | |
| 610Z | | | YJ | 0-0 | 27-32-31 | D04457P | DED | | | D04379P | DED | | | ALL | | |
| 611 | 16 | PQ | YK | 3-5 | 27-32-31 | D04457P | | 55 | FL | D04379P | 55 | FL | | ALL | | |
| 611Z | | | YK | 0-0 | 27-32-31 | D04457P | DED | | | D04379P | DED | | | ALL | | |
| 612 | 20 | PQ | YL | 4-0 | 27-32-31 | D04457P | | 34 | | D04323P | 8 | | | ALL | | |
| 612Z | | | YL | 0-0 | 27-32-31 | D04457P | DED | | | D04323P | DED | | | ALL | | |
| 613 | 24 | PK | | 3-4 | 77-35-11 | D11786A | B09 | | | TB0105F | C077 | 2 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 26

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 614 | 24 | | PK | 6-4 | 77-35-11 | D11786A | D13 | | | | D05247P | 14 | | | ALL |
| 615 | 22 | | PA | 2-9 | 77-35-11 | D11786A | D14 | | | | GDY0011 | D.. | 2 | | ALL |
| 616Y | 22 | | PJ | 2-10 | 27-41-11 | D04351P | 16 | | | | D04379P | 33 | | | ALL |
| 617 | 22 | | PA | 2-7 | 27-41-11 | D04351P | 15 | | | | D04367P | 15 | | | ALL |
| 619 | 20 | | PA | 2-5 | 34-45-11 | GDY0010 | D.. | 2 | | | D02463C | 11 | | | ALL |
| 620 | 24 | | PK | 0-7 | 22-11-12 | D00433B | B12 | | | | D00433B | D15 | | | ALL |
| 621 | 24 | | PK | 0-7 | 22-11-12 | D00433B | A12 | | | | D00433B | B15 | | | ALL |
| 623 | 22 | | PA | 7-3 | 34-45-12 | D06143P | 9 | | | | D02463F | C05 | | | 050-099, 150-152, 155-199, 275-299 |
| 623 | 22 | | PA | 6-11 | 34-45-12 | D04855P | 54 | | | | D02463F | C05 | | | 153-154 |
| 624 | 22 | | PA | 3-1 | 34-22-16 | D04457P | 29 | | | | D05603P | 41 | | | ALL |
| 625 | 20 | | PA | 5-3 | 34-45-11 | D04207P | 23 | | | | D02463C | 1 | | | ALL |
| 632 | 24 | | PK | 0-7 | 22-11-12 | D00433A | C11 | | | | D00433A | C12 | | | ALL |
| 634 | 24 | | PK | 0-7 | 22-11-12 | D00433B | J02 | | | | D00433B | J04 | | | ALL |
| 635 | 24 | | PV | ZJ | 5-0 | 73-21-17 | D11786A | A10 | | | D04351P | 8 | | | ALL |
| 635Z | | | | ZJ | 0-0 | 73-21-17 | D11786A | | | FA | D04351P | | | ZK | ALL |
| 636 | 24 | | PV | ZK | 5-0 | 73-21-17 | D11786A | A11 | | | D04351P | 7 | | | ALL |
| 636Z | | | | ZK | 0-0 | 73-21-17 | D11786A | | | FA | D04351P | | | ZK | ALL |
| 637 | 20 | | UA | | 2-9 | 73-21-17 | D11786A | | | FA | GDY0011 | S.. | 2 | | ALL |
| 648B | 24 | | PW | ZW | 3-10 | 22-32-12 | D00427A | D04 | | | TB0105F | C080 | 2 | | 050-099 |
| 648B | 24 | | PW | ZW | 3-10 | 22-32-12 | D00427A | D04 | | | TB0105F | C079 | 2 | | 150-199, 275-299 |
| 648R | 24 | | PW | ZW | 0-0 | 22-32-12 | D00427A | D03 | | | TB0105F | A080 | 2 | | 050-099 |
| 648R | 24 | | PW | ZW | 0-0 | 22-32-12 | D00427A | D03 | | | TB0105F | A079 | 2 | | 150-199, 275-299 |
| 648Z | | | | ZW | 0-0 | 22-32-12 | D00427A | DED | | | GDY0012 | S.. | 2 | | ALL |
| 652B | 24 | | PL | B | 7-4 | 22-31-12 | D00427A | A15 | | | D05259P | 4 | | | ALL |
| 652R | 24 | | PL | B | 0-0 | 22-31-12 | D00427A | B15 | | | D05259P | 3 | | | ALL |
| 653B | 22 | | PB | C | 4-7 | 22-31-12 | D00427A | A13 | | | GDY0009 | D.. | 2 | | ALL |
| 653R | 22 | | PB | C | 0-0 | 22-31-12 | D00427A | A14 | | | TB0105F | A053 | 2 | | ALL |
| 654B | 22 | | PB | D | 6-2 | 22-31-12 | D05259P | 6 | | | GDY0009 | D.. | 2 | | ALL |
| 654R | 22 | | PB | D | 0-0 | 22-31-12 | D05259P | 5 | | | TB0105F | A053 | 2 | | ALL |
| 655B | 24 | | PW | E | 4-2 | 22-32-11 | D00427B | J08 | | | TB0105H | 69 | 2 | | ALL |
| 655R | 24 | | PW | E | 0-0 | 22-32-11 | D00427B | K08 | | | TB0105H | 67 | 2 | | ALL |
| 655Z | | | | E | 0-0 | 22-32-11 | D00427B | DED | | | GDY0011 | S.. | 2 | | ALL |
| 656 | 20 | | UA | | 1-6 | 22-32-11 | D00427B | REF | | A6 | GDY0014 | S.. | 2 | | ALL |
| 656B | 24 | | PW | F | 3-4 | 22-32-11 | D00427B | B14 | | | TB0105G | 193 | 2 | | ALL |
| 656R | 24 | | PW | F | 0-0 | 22-32-11 | D00427B | A14 | | | TB0105G | 192 | 2 | | ALL |
| 656Z | | | | F | 0-0 | 22-32-11 | D00427B | REF | | A6 | TB0105G | DED | | | ALL |
| 657B | 24 | | PW | G | 3-9 | 22-32-11 | D00427B | B13 | | | TB0105F | C180 | 2 | | ALL |
| 657R | 24 | | PW | G | 0-0 | 22-32-11 | D00427B | A13 | | | TB0105F | A180 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0100
Page 27
May 20/2005



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | | |
| 657Z | | | | G | 0-0 | 22-32-11 | D00427B | DED | | | | GDY0012 | S.. | 2 | | ALL |
| 658B | 24 | PW | | H | 3-8 | 22-32-11 | D00427B | A15 | | | | TB0105F | C181 | 2 | | ALL |
| 658R | 24 | PW | | H | 0-0 | 22-32-11 | D00427B | B15 | | | | TB0105F | A181 | 2 | | ALL |
| 658Z | | | | H | 0-0 | 22-32-11 | D00427B | DED | | | | GDY0012 | S.. | 2 | | ALL |
| 659 | 20 | UA | | | 1-6 | 22-32-11 | D00427A | REF | | A9 | | GDX0014 | S.. | 2 | | ALL |
| 659B | 24 | PW | | I | 3-4 | 22-32-11 | D00427A | J01 | | | | TB0105H | 87 | 2 | | ALL |
| 659R | 24 | PW | | I | 0-0 | 22-32-11 | D00427A | J02 | | | | TB0105H | 85 | 2 | | ALL |
| 659Z | | | | I | 0-0 | 22-32-11 | D00427A | REF | | A9 | | TB0105H | DED | | | ALL |
| 660B | 24 | PW | | J | 6-2 | 22-32-11 | D04831P | 14 | | | | TB0105H | 87 | 2 | | ALL |
| 660R | 24 | PW | | J | 0-0 | 22-32-11 | D04831P | 13 | | | | TB0105H | 85 | 2 | | ALL |
| 660Z | | | | J | 0-0 | 22-32-11 | D04831P | 15 | | | | GDY0016 | S.. | 2 | | ALL |
| 661 | 20 | UA | | | 1-6 | 22-32-11 | D00427A | | | GX | | GDX0013 | S.. | 2 | | ALL |
| 661B | 24 | PW | | K | 4-10 | 22-32-11 | D00427A | A09 | | | | D04781P | 13 | | | ALL |
| 661R | 24 | PW | | K | 0-0 | 22-32-11 | D00427A | A08 | | | | D04781P | 12 | | | ALL |
| 661Z | | | | K | 0-0 | 22-32-11 | D00427A | | | GX | | D04781P | 14 | | | ALL |
| 662B | 24 | PW | | L | 6-6 | 22-32-11 | D00427A | A06 | | | | TB0105H | 17 | 2 | | ALL |
| 662R | 24 | PW | | L | 0-0 | 22-32-11 | D00427A | A07 | | | | TB0105H | 15 | 2 | | ALL |
| 662Z | | | | L | 0-0 | 22-32-11 | D00427A | DED | | | | GDY0002 | S.. | 2 | | ALL |
| 663 | 20 | UA | | | 1-6 | 22-32-12 | D00427B | REF | | B3 | | GDX0014 | S.. | 2 | | ALL |
| 663B | 24 | PW | | M | 3-3 | 22-32-12 | D00427B | J14 | | | | TB0105F | C184 | 2 | | ALL |
| 663R | 24 | PW | | M | 0-0 | 22-32-12 | D00427B | J15 | | | | TB0105F | A184 | 2 | | ALL |
| 663Z | | | | M | 0-0 | 22-32-12 | D00427B | REF | | B3 | | TB0105F | DED | | | ALL |
| 664B | 24 | PW | | N | 4-5 | 22-32-12 | D00427B | J13 | | | | TB0105H | 57 | 2 | | ALL |
| 664R | 24 | PW | | N | 0-0 | 22-32-12 | D00427B | J12 | | | | TB0105H | 55 | 2 | | ALL |
| 664Z | | | | N | 0-0 | 22-32-12 | D00427B | DED | | | | GDY0009 | S.. | 2 | | ALL |
| 666 | 20 | UA | | | 1-6 | 22-32-11 | D00427A | | | G4 | | GDX0013 | S.. | 2 | | ALL |
| 666B | 24 | PW | | P | 7-4 | 22-32-11 | D00427A | C03 | | | | D05259P | 14 | | | ALL |
| 666R | 24 | PW | | P | 0-0 | 22-32-11 | D00427A | C02 | | | | D05259P | 13 | | | ALL |
| 666Z | | | | P | 0-0 | 22-32-11 | D00427A | | | G4 | | D05259P | 9 | | | ALL |
| 671B | 24 | PL | | U | 6-8 | 22-32-13 | D00427A | K09 | | | | D04365P | 27 | | | ALL |
| 671R | 24 | PL | | U | 0-0 | 22-32-13 | D00427A | J09 | | | | D04365P | 26 | | | ALL |
| 673B | 24 | PL | | W | 6-6 | 22-32-13 | D00427B | J04 | | | | D04367P | 21 | | | ALL |
| 673R | 24 | PL | | W | 0-0 | 22-32-13 | D00427B | K04 | | | | D04367P | 20 | | | ALL |
| 677 | 20 | UA | | | 1-6 | 22-33-11 | D00427B | REF | | FB | | GDX0014 | S.. | 2 | | ALL |
| 677B | 24 | PW | | AZ | 3-4 | 22-33-11 | D00427B | A12 | | | | TB0105G | 194 | 2 | | ALL |
| 677R | 24 | PW | | AZ | 0-0 | 22-33-11 | D00427B | A11 | | | | TB0105G | 195 | 2 | | ALL |
| 677Z | | | | AZ | 0-0 | 22-33-11 | D00427B | REF | | FB | | TB0105G | DED | | | ALL |
| 678B | 24 | PL | | BZ | 7-0 | SPARE | D00427B | J02 | | | | D04457P | 12 | | | 150-199 |
| 678R | 24 | PL | | BZ | 0-0 | SPARE | D00427B | J03 | | | | D04457P | 11 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 28

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description FT-IN Diagram | From | | | To | | | Effectivity | | | | |
|------------------------|-----------------|----|----|--|------|----------|---------|------|--------|-------|-------------|------|------|--------|-----|
| | GA | CO | TY | | Fam | Equip | Term | Type | Splice | Equip | | Term | Type | Splice | |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 679 | 20 | | UA | | 1-6 | 22-33-11 | D00427B | REF | | FC | GDY0014 | S.. | 2 | | ALL |
| 679B | 24 | | PW | CZ | 3-4 | 22-33-11 | D00427B | K11 | | | TB0105G | 196 | 2 | | ALL |
| 679R | 24 | | PW | CZ | 0-0 | 22-33-11 | D00427B | J11 | | | TB0105G | 197 | 2 | | ALL |
| 679Z | | | | | 0-0 | 22-33-11 | D00427B | REF | | FC | TB0105G | DED | | | ALL |
| 682 | 20 | | UA | | 1-6 | 34-22-38 | D05655J | | | G8 | GDY0013 | S.. | 2 | | ALL |
| 682B | 24 | | PW | FZ | 4-8 | 34-22-38 | D05655J | 2 | | | D04831P | 2 | | | ALL |
| 682R | 24 | | PW | FZ | 0-0 | 34-22-38 | D05655J | 1 | | | D04831P | 1 | | | ALL |
| 682Z | | | | | 0-0 | 34-22-38 | D05655J | | | G8 | D04831P | 3 | | | ALL |
| 684B | 24 | | PW | HZ | 3-3 | 34-22-39 | D05655J | 5 | | | TB0105H | 57 | 2 | | ALL |
| 684R | 24 | | PW | HZ | 0-0 | 34-22-39 | D05655J | 4 | | | TB0105H | 55 | 2 | | ALL |
| 684Z | | | | | 0-0 | 34-22-39 | D05655J | 6 | | | GDY0009 | S.. | 2 | | ALL |
| 685B | 24 | | PW | D5 | 5-4 | 34-43-11 | D05603P | 24 | | | TB0105H | 87 | 2 | | ALL |
| 685R | 24 | | PW | D5 | 0-0 | 34-43-11 | D05603P | 23 | | | TB0105H | 85 | 2 | | ALL |
| 685Z | | | | | 0-0 | 34-43-11 | D05603P | 25 | | | GDY0016 | S.. | 2 | | ALL |
| 686B | 24 | | PW | JZ | 4-8 | 22-14-11 | D04591P | 11 | | | TB0105H | 57 | 2 | | ALL |
| 686R | 24 | | PW | JZ | 0-0 | 22-14-11 | D04591P | 10 | | | TB0105H | 55 | 2 | | ALL |
| 686Z | | | | | 0-0 | 22-14-11 | D04591P | 12 | | | GDY0009 | S.. | 2 | | ALL |
| 687B | 24 | | PW | KZ | 4-1 | 34-22-19 | D05603P | 33 | | | TB0105H | 57 | 2 | | ALL |
| 687R | 24 | | PW | KZ | 0-0 | 34-22-19 | D05603P | 32 | | | TB0105H | 55 | 2 | | ALL |
| 687Z | | | | | 0-0 | 34-22-19 | D05603P | 34 | | | GDY0009 | S.. | 2 | | ALL |
| 689B | 24 | | PW | MZ | 3-9 | 22-32-12 | D00427B | G06 | | | TB0105G | 179 | 2 | | ALL |
| 689R | 24 | | PW | MZ | 0-0 | 22-32-12 | D00427B | H06 | | | TB0105G | 178 | 2 | | ALL |
| 689Z | | | | | 0-0 | 22-32-12 | D00427B | DED | | | GDY0012 | S.. | 2 | | ALL |
| 690B | 24 | | PW | NZ | 3-5 | 34-61-12 | D04781P | 19 | | | TB0105H | 57 | 2 | | ALL |
| 690R | 24 | | PW | NZ | 0-0 | 34-61-12 | D04781P | 18 | | | TB0105H | 55 | 2 | | ALL |
| 690Z | | | | | 0-0 | 34-61-12 | D04781P | 20 | | | GDY0009 | S.. | 2 | | ALL |
| 691B | 24 | | PW | OZ | 4-7 | 22-32-12 | TB0105G | 179 | 2 | | D05603P | 10 | | | ALL |
| 691R | 24 | | PW | OZ | 0-0 | 22-32-12 | TB0105G | 178 | 2 | | D05603P | 9 | | | ALL |
| 691Z | | | | | 0-0 | 22-32-12 | GDY0012 | S.. | 2 | | D05603P | 11 | | | ALL |
| 692B | 24 | | PW | PZ | 3-4 | 22-41-12 | D00427A | F01 | | | TB0105G | 84 | 2 | | ALL |
| 692R | 24 | | PW | PZ | 0-0 | 22-41-12 | D00427A | F02 | | | TB0105G | 83 | 2 | | ALL |
| 692Z | | | | | 0-0 | 22-41-12 | D00427A | DED | | | GDY0016 | S.. | 2 | | ALL |
| 693 | 20 | | UA | | 2-9 | 31-31-14 | D11786B | | | QZ | GDY0011 | S.. | 2 | | ALL |
| 693B | 24 | | PW | QZ | 7-2 | 31-31-14 | D04855P | 2 | | | D11786B | A15 | | | ALL |
| 693R | 24 | | PW | QZ | 0-0 | 31-31-14 | D04855P | 1 | | | D11786B | A14 | | | ALL |
| 693Z | | | | | 0-0 | 31-31-14 | D04855P | 3 | | | D11786B | | | QZ | ALL |
| 694B | 24 | | PW | RZ | 2-11 | 31-41-31 | D05247P | 16 | | | D05603P | 21 | | | ALL |
| 694R | 24 | | PW | RZ | 0-0 | 31-41-31 | D05247P | 15 | | | D05603P | 20 | | | ALL |
| 694Z | | | | | 0-0 | 31-41-31 | D05247P | 17 | | | D05603P | 22 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0100
Page 29
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|-----------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | | | |
| 695B | 24 | PW | SZ | | 3-2 | 31-41-31 | D05247P | | 19 | | | | TB0105H | 6 | 2 | | ALL |
| 695R | 24 | PW | SZ | | 0-0 | 31-41-31 | D05247P | | 18 | | | | TB0105H | 4 | 2 | | ALL |
| 695Z | | | SZ | | 0-0 | 31-41-31 | D05247P | | 20 | | | | GDY0001 | S.. | 2 | | ALL |
| 697B | 24 | PL | UZ | | 7-4 | 22-31-12 | D05259P | | 8 | | | | D00427B | A03 | | | ALL |
| 697R | 24 | PL | UZ | | 0-0 | 22-31-12 | D05259P | | 7 | | | | D00427B | A02 | | | ALL |
| 698B | 24 | PW | VZ | | 2-11 | 22-41-13 | D05603P | | 36 | | | | D05247P | 9 | | | ALL |
| 698R | 24 | PW | VZ | | 0-0 | 22-41-13 | D05603P | | 35 | | | | D05247P | 8 | | | ALL |
| 698Z | | | VZ | | 0-0 | 22-41-13 | D05603P | | 37 | | | | D05247P | 10 | | | ALL |
| 699B | 24 | PW | WZ | | 5-5 | 22-32-12 | TB0105G | | 179 | 2 | | | D05247P | 5 | | | ALL |
| 699R | 24 | PW | WZ | | 0-0 | 22-32-12 | TB0105G | | 178 | 2 | | | D05247P | 4 | | | ALL |
| 699Z | | | WZ | | 0-0 | 22-32-12 | GDY0012 | | S.. | 2 | | | D05247P | 6 | | | ALL |
| 700 | 24 | PK | | | 3-1 | 22-32-14 | TB0105H | | 78 | 2 | | | TB0105H | 81 | 2 | | 050-099 |
| 700 | 24 | PK | | | 3-1 | 22-32-14 | TB0105G | | 78 | 2 | | | TB0105H | 81 | 2 | | 150-199 |
| 700 | 24 | PK | | | 3-5 | 22-32-14 | TB0105H | | 163 | 2 | | | TB0105H | 81 | 2 | | 275-299 |
| 701 | 20 | PA | | | 6-6 | 22-31-11 | D04207P | | 4 | | | | TB0105G | 89 | 2 | | ALL |
| 702 | 20 | PA | | | 3-4 | 22-31-11 | D00427C | | 10 | | | | TB0105G | 89 | 2 | | ALL |
| 703 | 20 | PA | | | 6-8 | 22-31-11 | D00427C | | 6 | | | | D04365P | 16 | | | ALL |
| 704 | 20 | PA | | | 2-5 | 22-31-11 | D00427C | | 8 | | | | GDY0013 | S.. | 2 | | ALL |
| 705 | 20 | PA | | | 2-5 | 22-31-11 | D00427C | | 3 | | | | GDY0013 | A.. | 2 | | ALL |
| 706 | 24 | PK | | | 6-8 | 22-31-11 | D04365P | | 17 | | | | TB0105G | 89 | 2 | | ALL |
| 709 | 20 | PA | | | 3-3 | 22-31-12 | D00427C | | 5 | | | | TB0105G | 187 | 2 | | ALL |
| 70L | 20 | PA | | | 6-0 | 29-11-14 | D04457P | | 28 | | | | D04351P | 4 | | | ALL |
| 70M | 20 | PQ | CT | | 6-0 | 29-11-14 | D04457P | | 24 | | | | D04351P | 18 | | | ALL |
| 70MZ | | | CT | | 0-0 | 29-11-14 | D04457P | | DED | | | | D04351P | DED | | | ALL |
| 70N | 20 | PA | | | 3-5 | 29-11-14 | D04457P | | 15 | | | | D04379P | 51 | | | ALL |
| 70P | 20 | PA | | | 3-5 | 29-11-14 | D04457P | | 21 | | | | D04379P | 54 | | | ALL |
| 711 | 22 | PA | | | 2-5 | 22-31-12 | D00427A | | K03 | | | | GDY0013 | D.. | 2 | | ALL |
| 712 | 22 | PA | | | 4-4 | 22-32-14 | D00427B | | F02 | | | | TB0105H | 152 | # | | 050-099 |
| 712 | 22 | PA | | | 3-0 | 22-32-14 | D00427B | | F02 | | | | GDY0012 | D.. | 2 | | 150-199 |
| 712 | 22 | PA | | | 4-4 | 22-32-14 | D00427B | | F02 | | | | TB0105H | 152 | 2 | | 275-299 |
| 713 | 22 | PA | | | 6-3 | 34-45-13 | D04457P | | 13 | | | | D02463E | K05 | | | ALL |
| 714 | 24 | PK | | | 5-5 | 22-32-13 | D04365P | | 22 | | | | TB0105H | 81 | 2 | | ALL |
| 715 | 24 | PK | | | 6-8 | 22-32-13 | D04365P | | 23 | | | | D00427B | H07 | | | ALL |
| 716 | 20 | PA | | | 4-6 | 22-32-13 | D04365P | | 24 | | | | GDY0010 | D.. | 2 | | ALL |
| 717 | 24 | PK | | | 3-9 | 22-32-13 | D00427B | | H09 | | | | TB0105H | 81 | 2 | | ALL |
| 720 | 22 | PA | | | 4-4 | 22-32-14 | D00427B | | D10 | | | | TB0105H | 152 | 2 | | 050-099, 275-299 |
| 720 | 22 | PA | | | 3-0 | 22-32-14 | D00427B | | D10 | | | | GDY0012 | D.. | 2 | | 150-199 |
| 721 | 22 | PA | | | 4-4 | 22-32-14 | D00427B | | F06 | | | | TB0105H | 152 | 2 | | 050-099, 275-299 |
| 721 | 22 | PA | | | 3-0 | 22-32-14 | D00427B | | F06 | | | | GDY0012 | D.. | 2 | | 150, 152-165, 167-199 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 30

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 721 | 22 | | PA | 3-0 | 22-32-14 | D00427B | F06 | | | | GDX0012 | CAP | Y | | 151, 166 |
| 722 | 22 | | PA | 4-4 | 22-32-14 | D00427B | G11 | | | | TB0105H | 152 | 2 | | 050-099, 275-299 |
| 722 | 22 | | PA | 3-0 | 22-32-14 | D00427B | G11 | | | | GDX0012 | D.. | 2 | | 150-199 |
| 723 | 22 | | PA | 4-4 | 22-32-14 | D00427B | C01 | | | | TB0105H | CAP | Y | | 050-099 |
| 723 | 22 | | PA | 3-0 | 22-32-14 | D00427B | C01 | | | | GDX0012 | D.. | # | | 150-166 |
| 723 | 22 | | PA | 3-0 | 22-32-14 | D00427B | C01 | | | | GDX0012 | CAP | Y | | 167-199 |
| 723 | 22 | | PA | 4-4 | 22-32-14 | D00427B | C01 | | | | TB0105H | 152 | # | | 275-299 |
| 724 | 22 | | PA | 4-7 | 22-32-14 | D00427A | E15 | | | | TB0105H | 150 | 2 | | 050-099, 275-299 |
| 724 | 22 | | PA | 3-0 | 22-32-14 | D00427A | E15 | | | | GDX0012 | D.. | 2 | | 150-199 |
| 725 | 22 | | PA | 4-4 | 22-32-14 | D00427A | D13 | | | | TB0105H | 150 | 2 | | 050-099 |
| 725 | 22 | | PA | 2-5 | 22-32-14 | D00427A | D13 | | | | GDX0013 | D.. | 2 | | 150, 152-165, 167-199 |
| 725 | 22 | | PA | 2-5 | 22-32-14 | D00427A | D13 | | | | GDX0013 | CAP | Y | | 151, 166 |
| 725 | 22 | | PA | 4-7 | 22-32-14 | D00427A | D13 | | | | TB0105H | 150 | 2 | | 275-299 |
| 726 | 22 | | PA | 3-9 | 22-32-14 | D00427A | F07 | | | | TB0105H | 81 | 2 | | 050-099, 275-299 |
| 726 | 22 | | PA | 3-10 | 22-32-14 | D00427A | F07 | | | | TB0105G | 78 | 2 | | 150-199 |
| 727 | 22 | | PA | 3-10 | 22-32-14 | D00427A | F09 | | | | TB0105H | 78 | 2 | | 050-099 |
| 727 | 22 | | PA | 3-10 | 22-32-14 | D00427A | F09 | | | | TB0105G | 78 | 2 | | 150-199 |
| 727 | 22 | | PA | 4-2 | 22-32-14 | D00427A | F09 | | | | TB0105H | 163 | 2 | | 275-299 |
| 728 | 22 | | PA | 3-10 | 22-32-14 | D00427A | K05 | | | | TB0105H | 78 | 2 | | 050-099 |
| 728 | 22 | | PA | 3-9 | 22-32-14 | D00427A | K05 | | | | TB0105H | 81 | 2 | | 150-199 |
| 728 | 22 | | PA | 4-2 | 22-32-14 | D00427A | K05 | | | | TB0105H | 163 | 2 | | 275-299 |
| 729 | 22 | | PA | 3-10 | 22-32-14 | D00427B | H10 | | | | TB0105H | 78 | 2 | | 050-099 |
| 729 | 22 | | PA | 3-10 | 22-32-14 | D00427B | H10 | | | | TB0105G | 78 | 2 | | 150-199 |
| 729 | 22 | | PA | 4-2 | 22-32-14 | D00427B | H10 | | | | TB0105H | 163 | 2 | | 275-299 |
| 731 | 20 | | PA | 3-6 | 22-32-13 | D04895P | 1 | | | | GDX0010 | D.. | 2 | | ALL |
| 732 | 24 | | PK | 3-11 | 22-32-13 | D04895P | 2 | | | | TB0105H | 81 | 2 | | ALL |
| 733 | 24 | | PK | 6-6 | 22-32-13 | D00427B | D06 | | | | D04367P | 8 | | | ALL |
| 734 | 24 | | PK | 3-7 | 22-32-13 | D00427B | H02 | | | | D04895P | 4 | | | ALL |
| 735 | 24 | | PK | 3-7 | 22-32-13 | D00427B | D05 | | | | D04895P | 5 | | | ALL |
| 736 | 24 | | PK | 3-7 | 22-32-13 | D00427A | F05 | | | | D04895P | 6 | | | ALL |
| 737 | 24 | | PK | 3-7 | 22-32-13 | D00427A | F04 | | | | D04895P | 7 | | | ALL |
| 738 | 24 | | PK | 6-6 | 22-32-13 | D00427A | K02 | | | | D04367P | 10 | | | ALL |
| 739 | 24 | | PK | 6-6 | 22-32-13 | D00427A | J03 | | | | D04367P | 9 | | | ALL |
| 740 | 24 | | PK | 3-7 | 22-32-13 | D00427A | K10 | | | | D04895P | 8 | | | ALL |
| 741 | 24 | | PK | 6-6 | 22-32-13 | D00427B | H08 | | | | D04367P | 11 | | | ALL |
| 742 | 22 | | PA | 3-10 | 22-32-14 | D00427A | H06 | | | | TB0105H | 78 | 2 | | 050-099 |
| 742 | 22 | | PA | 3-9 | 22-32-14 | D00427A | H06 | | | | TB0105H | 81 | 2 | | 150-199 |
| 742 | 22 | | PA | 4-2 | 22-32-14 | D00427A | H06 | | | | TB0105H | 163 | 2 | | 275-299 |
| 743 | 22 | | PA | 4-7 | 22-32-14 | D00427A | F03 | | | | TB0105H | 150 | 2 | | 050-099, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 31

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | | | |
| 743 | 22 | | PA | 2-5 | 22-32-14 | D00427A | F03 | | | | | | GDX0013 | D.. | 2 | | 150-199 |
| 744 | 22 | | PA | 4-7 | 22-32-14 | D00427A | J12 | | | | | | TB0105H | 150 | 2 | | 050-099, 275-299 |
| 744 | 22 | | PA | 2-5 | 22-32-14 | D00427A | J12 | | | | | | GDX0013 | D.. | 2 | | 150-199 |
| 745 | 24 | | PK | 6-6 | 22-32-13 | D00427B | G02 | | | | | | D04367P | 12 | | | ALL |
| 746 | 24 | | PK | 6-8 | 22-32-15 | D00427B | F05 | | | | | | D04365P | 3 | | | ALL |
| 747 | 24 | | PK | 6-8 | 22-32-15 | D00427A | G15 | | | | | | D04365P | 35 | | | ALL |
| 748 | 24 | | PK | 3-9 | 22-32-15 | D00427A | K06 | | | | | | TB0105H | 81 | 2 | | ALL |
| 750 | 24 | | PK | 6-6 | 22-32-15 | D04591P | 13 | | | | | | D00427C | 1 | | | ALL |
| 755 | 20 | | PA | 4-6 | 22-32-15 | D04365P | 34 | | | | | | GDX0010 | D.. | 2 | | ALL |
| 757 | 20 | | PA | 4-10 | 22-32-15 | D04457P | 7 | | | | | | GDX0010 | D.. | 2 | | ALL |
| 758 | 24 | | PK | 4-10 | 22-32-15 | D00427B | F01 | | | | | | TB0105G | 39 | 2 | | ALL |
| 759 | 24 | | PK | 3-4 | 22-32-15 | D00427A | D01 | | | | | | TB0105G | 96 | 2 | | ALL |
| 760 | 24 | | PK | 6-6 | 22-32-15 | TB0105G | 96 | 2 | | | | | D04591P | 14 | | | ALL |
| 761 | 24 | | PK | 7-0 | 22-32-15 | D00427B | C07 | | | | | | D04457P | 8 | | | ALL |
| 762 | 22 | | PA | 6-4 | 22-34-11 | D04169P | 10 | | | | | | TB0105G | 185 | 2 | | ALL |
| 763 | 22 | | PA | 3-3 | 22-34-11 | D00427B | D13 | | | | | | TB0105G | 185 | 2 | | ALL |
| 764 | 22 | | PA | 3-3 | 22-34-11 | D00427B | B03 | | | | | | TB0105G | 185 | 2 | | ALL |
| 765 | 24 | | PK | 3-4 | 22-34-11 | D00427B | D09 | | | | | | TB0105G | 93 | 2 | | ALL |
| 766 | 24 | | PK | 3-4 | 22-34-11 | D00427B | D08 | | | | | | TB0105G | 93 | 2 | | ALL |
| 768 | 22 | | PA | 4-4 | 22-32-14 | D00427A | D12 | | | | | | TB0105H | 154 | 2 | | 050-099, 275-299 |
| 768 | 22 | | PA | 3-0 | 22-32-14 | D00427A | D12 | | | | | | GDX0012 | D.. | 2 | | 150-199 |
| 769 | 22 | | PA | 5-5 | 22-32-12 | D00427B | C15 | | | | | | D05603P | 12 | | | ALL |
| 770 | 20 | | PA | 2-5 | 22-31-12 | D00427C | 7 | | | | | | GDX0013 | D.. | 2 | | ALL |
| 772 | 22 | | PA | 4-4 | 22-32-14 | D00427A | G08 | | | | | | TB0105H | 154 | # | | 050-099, 275-299 |
| 772 | 22 | | PA | 3-0 | 22-32-14 | D00427A | G08 | | | | | | GDX0012 | D.. | # | | 150-166 |
| 772 | 22 | | PA | 3-0 | 22-32-14 | D00427A | G08 | | | | | | GDX0012 | CAP | Y | | 167-199 |
| 773 | 22 | | PA | 4-4 | 22-32-14 | D00427A | D11 | | | | | | TB0105H | 154 | 2 | | 050-099, 275-299 |
| 773 | 22 | | PA | 3-0 | 22-32-14 | D00427A | D11 | | | | | | GDX0012 | D.. | 2 | | 150-199 |
| 774 | 22 | | PA | 4-4 | 22-32-14 | D00427A | C11 | | | | | | TB0105H | 154 | 2 | | 050-099, 275-299 |
| 774 | 22 | | PA | 3-0 | 22-32-14 | D00427A | C11 | | | | | | GDX0012 | D.. | 2 | | 150-199 |
| 775 | 22 | | PA | 4-4 | 22-32-14 | D00427A | D10 | | | | | | TB0105H | 154 | 2 | | 050-099, 275-299 |
| 775 | 22 | | PA | 3-0 | 22-32-14 | D00427A | D10 | | | | | | GDX0012 | D.. | 2 | | 150-199 |
| 776 | 22 | | PA | 4-7 | 22-32-14 | D00427A | B11 | | | | | | TB0105H | 150 | # | | 050-099, 275-299 |
| 776 | 22 | | PA | 3-0 | 22-32-14 | D00427A | B11 | | | | | | GDX0012 | D.. | # | | 150-166 |
| 776 | 22 | | PA | 3-0 | 22-32-14 | D00427A | B11 | | | | | | GDX0012 | CAP | Y | | 167-199 |
| 777 | 22 | | PA | 4-7 | 22-32-14 | D00427A | E14 | | | | | | TB0105H | 150 | 2 | | 050-099, 275-299 |
| 777 | 22 | | PA | 3-0 | 22-32-14 | D00427A | E14 | | | | | | GDX0012 | D.. | 2 | | 150-199 |
| 778 | 22 | | PA | 4-4 | 22-32-14 | D00427B | F04 | | | | | | TB0105H | 152 | # | | 050-099, 275-299 |
| 778 | 22 | | PA | 3-0 | 22-32-14 | D00427B | F04 | | | | | | GDX0012 | D.. | # | | 150-166 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 32

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 778 | 22 | | PA | | 3-0 | 22-32-14 | D00427B | F04 | | | GDX0012 | CAP | Y | | 167-199 |
| 779 | 22 | | PA | | 4-1 | 34-45-13 | TB0105G | 186 | 2 | | D02463E | CAP | Y | | 050-099, 150-166, 275-276 |
| 780 | 22 | | PA | | 4-8 | 34-45-13 | D05653P | | 4 | | D02463E | F13 | | | ALL |
| 781 | 22 | | PA | | 4-7 | 22-32-14 | D00427A | | H15 | | TB0105H | 150 | 2 | | 050-099 |
| 781 | 22 | | PA | | 3-0 | 22-32-14 | D00427A | | H15 | | GDX0012 | D.. | # | | 150-166 |
| 781 | 22 | | PA | | 3-0 | 22-32-14 | D00427A | | H15 | | GDX0012 | CAP | Y | | 167-199 |
| 781 | 22 | | PA | | 4-7 | 22-32-14 | D00427A | | H15 | | TB0105H | 150 | # | | 275-299 |
| 782 | 20 | | UA | | 1-6 | 34-45-13 | GDX0010 | S.. | 2 | | D02463E | REF | | O2 | ALL |
| 782B | 22 | | PR | O2 | 5-4 | 34-45-13 | D04591P | | 28 | | D02463E | G03 | | | 050-099, 153-199, 277-299 |
| 782B | 22 | | PR | O2 | 5-4 | 34-45-13 | D04591P | | 17 | | D02463E | G03 | | | 150-152, 275-276 |
| 782R | 22 | | PR | O2 | 0-0 | 34-45-13 | D04591P | | 27 | | D02463E | F03 | | | 050-099, 153-199, 277-299 |
| 782R | 22 | | PR | O2 | 0-0 | 34-45-13 | D04591P | | 16 | | D02463E | F03 | | | 150-152, 275-276 |
| 782Z | | | | O2 | 0-0 | 34-45-13 | D04591P | | 29 | | D02463E | REF | | O2 | 050-099, 153-199, 277-299 |
| 782Z | | | | O2 | 0-0 | 34-45-13 | D04591P | | 24 | | D02463E | REF | | O2 | 150-152, 275-276 |
| 784 | 24 | | PK | | 5-1 | 34-45-13 | TB0105G | | 110 | 2 | D02463E | K13 | | | ALL |
| 785 | 22 | | PA | | 4-4 | 34-45-14 | D04169P | | 35 | | TB0105G | 47 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 785 | 22 | | PA | | 4-7 | 34-45-14 | D04169P | | 35 | | TB0105G | 54 | 2 | | 157, 167-199, 277-299 |
| 786 | 22 | | PA | | 5-2 | 34-45-14 | D04169P | | 39 | | D02463E | CAP | Y | | 050-099, 150-156, 162-166, 275-276 |
| 788 | 20 | | PA | | 2-7 | 22-32-14 | TB0105H | | 154 | 2 | GDX0007 | D.. | 2 | | 050-099, 275-299 |
| 789 | 20 | | PA | | 2-5 | 22-32-14 | TB0105H | | 150 | 2 | GDX0007 | D.. | 2 | | 050-099, 275-299 |
| 790 | 20 | | PA | | 2-7 | 22-32-14 | TB0105H | | 152 | 2 | GDX0007 | D.. | 2 | | 050-099, 275-299 |
| 802 | 20 | | PQ | Q2 | 4-5 | 34-12-11 | D00423C | | 1 | | TB0105G | 139 | 2 | | ALL |
| 802Z | | | | Q2 | 0-0 | 34-12-11 | D00423C | | DED | | TB0105G | DED | | | ALL |
| 803 | 16 | | PA | | 4-6 | 34-12-11 | D00423C | | 7 | | GDY0007 | A.. | 2 | | 050-099, 277-299 |
| 803 | 16 | | PA | | 4-9 | 34-12-11 | D00423C | | 7 | | GDY0008 | A.. | 2 | | 150-199, 275-276 |
| 804 | 16 | | PA | | 4-6 | 34-12-11 | D00423C | | 8 | | GDY0007 | D.. | 2 | | 050-099, 277-299 |
| 804 | 16 | | PA | | 4-9 | 34-12-11 | D00423C | | 8 | | GDY0008 | D.. | 2 | | 150-199, 275-276 |
| 810 | 24 | | PK | | 7-0 | 34-12-12 | D05383P | | 3 | | D04457P | 16 | | | ALL |
| 811 | 22 | | PA | | 2-9 | 34-12-12 | D00423B | | J06 | | GDX0002 | D.. | 2 | | ALL |
| 812 | 24 | | PK | | 3-10 | 34-12-12 | D00423B | | F02 | | D04457P | 17 | | | ALL |
| 813 | 24 | | PK | | 3-6 | 34-12-12 | TB0105G | | 111 | 2 | D04457P | 18 | | | ALL |
| 814 | 24 | | PK | | 3-10 | 34-12-12 | D00423B | | E09 | | D04457P | 19 | | | ALL |
| 816 | 22 | | PA | | 0-7 | 34-12-12 | D00423B | | D14 | | D00423B | K14 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 33

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | | | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | |
| 816 | 22 | | PA | 0-7 | 34-12-12 | D00423B | D14 | | | | D00423B | G14 | | | 150-199, 275-299 |
| 817 | 24 | | PK | 2-11 | 34-12-12 | D00423B | E03 | | | | TB0105G | 2 | 2 | | ALL |
| 818 | 24 | | PK | 3-10 | 34-12-12 | D00423B | E10 | | | | D04457P | 20 | | | ALL |
| 820 | 24 | | PK | 4-0 | 34-12-12 | D05259P | 27 | | | | TB0105H | 107 | 2 | | ALL |
| 822 | 22 | | PA | 4-2 | 34-12-12 | D00423B | H15 | | | | TB0105H | 130 | 2 | | ALL |
| 823 | 24 | | PK | 3-7 | 31-51-21 | D04323P | 11 | | | | TB0105H | 107 | 2 | | ALL |
| 828 | 24 | | PK | 3-1 | 34-12-12 | D00423B | F11 | | | | TB0105G | 111 | 2 | | ALL |
| 829 | 24 | | PK | 3-10 | 34-12-12 | D00423B | F10 | | | | D04457P | 23 | | | ALL |
| 830 | 24 | | PK | 4-2 | 34-12-12 | D04855P | 38 | | | | TB0105G | 111 | 2 | | ALL |
| 831 | 22 | | PA | 4-2 | 34-12-12 | D00423B | F15 | | | | TB0105H | 130 | 2 | | ALL |
| 832 | 22 | | PA | 2-9 | 34-12-12 | D00423B | D06 | | | | GDY0002 | D.. | 2 | | ALL |
| 837 | 22 | | PA | 3-9 | 22-32-14 | D00427A | J10 | | | | TB0105H | 81 | 2 | | ALL |
| 850 | 22 | | PA | 4-2 | 34-12-12 | D00423B | F05 | | | | TB0105H | 130 | 2 | | ALL |
| 854 | 24 | | PK | 6-9 | 22-34-11 | TB0105G | 93 | 2 | | | D05247P | 7 | | | ALL |
| 855 | 22 | | PA | 4-9 | 34-21-11 | D04831P | 30 | | | | D05247P | 11 | | | ALL |
| 856 | 22 | | PA | 4-9 | 34-21-11 | D04831P | 31 | | | | D05247P | 12 | | | ALL |
| 857 | 22 | | PA | 4-9 | 34-21-11 | D04831P | 32 | | | | D05247P | 13 | | | ALL |
| 858 | 22 | | PA | 6-9 | 31-51-33 | D05383P | 17 | | | | D04365P | 55 | | | ALL |
| 859 | 24 | | PK | 6-9 | 31-51-33 | D05383P | 18 | | | | D04365P | 50 | | | ALL |
| 860 | 24 | | PK | 6-9 | 31-51-33 | D05383P | 19 | | | | D04365P | 51 | | | ALL |
| 861 | 24 | | PK | 6-5 | 34-46-12 | D04169P | 8 | | | | D05383P | 21 | | | ALL |
| 862 | 22 | | PA | 2-5 | 22-32-13 | D00427B | E08 | | | | GDY0013 | D.. | 2 | | ALL |
| 863 | 22 | | PA | 4-2 | 34-12-12 | D00423B | D02 | | | | TB0105H | 130 | 2 | | ALL |
| 864 | 22 | | PA | 4-2 | 34-12-12 | D00423B | G03 | | | | TB0105H | 130 | 2 | | ALL |
| 865 | 22 | | PA | 4-2 | 34-12-12 | D00423B | K15 | | | | TB0105H | 130 | 2 | | 050-099 |
| 889 | 24 | | PK | 7-0 | 31-31-15 | D04351P | 12 | | | | D04855P | 11 | | | 050-099, 155-199, 275-299 |
| 889 | 24 | | PK | 4-7 | 31-31-15 | D04365P | 40 | | | | D04855P | 11 | | | 150-154 |
| 890 | 24 | | PK | 8-0 | 31-31-19 | D04855P | 17 | | | | TB0105Z | CAP | Y | | 050-099 |
| 890 | 24 | | PK | 6-0 | 31-31-19 | D04855P | 17 | | | | TB0105Z | 44 | % | | 150-199, 275-299 |
| 892 | 22 | | PA | 3-0 | 31-31-25 | D04337P | 25 | | | | D05247P | 24 | | | 050-099, 150-199 |
| 893 | 22 | | PA | 3-0 | 31-31-25 | D04337P | 28 | | | | D05247P | 36 | | | 050-099, 150-199 |
| 894B | 24 | | PW | Z4 | 4-2 | 34-21-21 | D04831P | 9 | | | TB0105H | 51 | 2 | | ALL |
| 894R | 24 | | PW | Z4 | 0-0 | 34-21-21 | D04831P | 8 | | | TB0105H | 49 | 2 | | ALL |
| 894Z | | | | Z4 | 0-0 | 34-21-21 | D04831P | 29 | | | GDY0008 | S.. | 2 | | 050-099, 277-299 |
| 894Z | | | | Z4 | 0-0 | 34-21-21 | D04831P | 29 | | | GDY0009 | S.. | 2 | | 150-199, 275-276 |
| 895B | 24 | | PW | Z5 | 4-4 | 34-13-11 | D04169P | 22 | | | TB0105H | 148 | 2 | | ALL |
| 895R | 24 | | PW | Z5 | 0-0 | 34-13-11 | D04169P | 21 | | | TB0105H | 146 | 2 | | ALL |
| 895Z | | | | Z5 | 0-0 | 34-13-11 | D04169P | 23 | | | GDY0008 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 34

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0105 | 286T0105 | E1-3 SHELF, LEFT SIDE (continued) | | | | | | | | | | | | | |
| 896B | 24 | PW | Z6 | | 4-1 | 27-11-22 | D05391P | | 9 | | TB0105H | 51 | 2 | | ALL |
| 896R | 24 | PW | Z6 | | 0-0 | 27-11-22 | D05391P | | 8 | | TB0105H | 49 | 2 | | ALL |
| 896Z | | | Z6 | | 0-0 | 27-11-22 | D05391P | | 10 | | GDY0008 | S.. | 2 | | 050-099, 277-299 |
| 896Z | | | Z6 | | 0-0 | 27-11-22 | D05391P | | 10 | | GDY0009 | S.. | 2 | | 150-199, 275-276 |
| 897B | 24 | PW | Z7 | | 4-1 | 22-21-21 | D04831P | | 39 | | D05391P | | 6 | | ALL |
| 897R | 24 | PW | Z7 | | 0-0 | 22-21-21 | D04831P | | 38 | | D05391P | | 5 | | ALL |
| 897Z | | | Z7 | | 0-0 | 22-21-21 | D04831P | | 40 | | D05391P | | 7 | | ALL |
| 901 | 22 | PA | | | 5-1 | 34-45-12 | D02463F | | J08 | | TB0105H | 112 | 2 | | ALL |
| 902 | 22 | PA | | | 5-1 | 34-45-12 | D02463F | | K08 | | TB0105H | 112 | 2 | | ALL |
| 903 | 22 | PA | | | 3-7 | 34-45-14 | TB0105G | | 158 | 2 | D02463E | J07 | | | 050-099, 150-152, 155-199, 275-299 |
| 904 | 22 | PA | | | 3-11 | 34-45-14 | TB0105G | | 47 | 2 | D02463E | E07 | | | 050-099, 150-156, 162-166, 275-276 |
| 904 | 22 | PA | | | 3-8 | 34-45-14 | TB0105G | | 54 | 2 | D02463E | E07 | | | 157, 277-299 |
| 905 | 22 | PA | | | 5-1 | 34-45-12 | D02463F | | F08 | | TB0105H | 112 | 2 | | ALL |
| 906 | 22 | PA | | | 5-1 | 34-45-12 | D02463F | | A07 | | TB0105H | 112 | 2 | | ALL |
| 907 | 22 | PA | | | 5-1 | 34-45-12 | D02463F | | C07 | | TB0105H | 112 | 2 | | ALL |
| 986B | 24 | PW | BO | | 0-0 | 34-53-11 | D04323P | | 10 | | TB0105H | 69 | 2 | | 275-299 |
| 986R | 24 | PW | BO | | 5-0 | 34-53-11 | D04323P | | 9 | | TB0105H | 67 | 2 | | 275-299 |
| 986Z | | | BO | | 0-0 | 34-53-11 | D04323P | | 12 | | GDY0011 | S.. | 2 | | 275-299 |
| FRA | | | | | 0-0 | 34-22-38 | D05655J | | | | D05655J | 3 | | | ALL |
| FRB | | | | | 0-0 | 73-21-17 | D04351P | | 3 | | D04351P | | | ZK | 050-099, 150-199, 277-299 |
| W0106 | 286T0106 | AFT CABIN LEFT FWD (G) | | | | | | | | | | | | | |
| 020 | 22 | PA | | | 5-0 | 33-22-42 | SM00011 | | 9 | | D06042P | 11 | | | 275-299 |
| 021 | 22 | PA | | | 5-0 | 33-22-42 | SM00010 | | 9 | | D06042P | 12 | | | 275-299 |
| 022 | 22 | PA | | | 5-0 | 33-22-42 | L00223 | =G | E | * | D02860 | 8 | | | 275-299 |
| 025 | 22 | PA | | | 5-0 | 33-22-42 | D06042P | | 13 | | L00223 | =G | E | * | 275-299 |
| 029 | 22 | PA | | | 5-0 | 33-22-42 | D02860 | | 9 | | L00223 | =1 | C | | 275-299 |
| 030 | 22 | PA | | | 5-0 | 33-22-42 | D02860 | | 10 | | L00223 | =2 | C | | 275-299 |
| 031 | 22 | PA | | | 3-0 | 33-22-42 | D02860 | | 11 | | SM00010 | | 9 | | 275-299 |
| 032 | 22 | PA | | | 3-0 | 33-22-42 | D02860 | | 12 | | SM00011 | | 9 | | 275-299 |
| 038 | 22 | PA | | | 5-0 | 33-22-42 | D02860 | | 5 | | D06042P | 19 | | | 275-299 |
| 039 | 22 | PA | | | 5-0 | 33-22-42 | D02860 | | 2 | | D06042P | 16 | | | 275-299 |
| 040 | 22 | PA | | | 5-0 | 33-22-42 | D02860 | | 3 | | D06042P | 17 | | | 275-299 |
| 041 | 22 | PA | | | 5-0 | 33-22-42 | D02860 | | 7 | | D06042P | 20 | | | 275-299 |
| 042 | 22 | PA | | | 5-0 | 33-22-42 | D02862 | | 5 | | D06042P | 21 | | | 275-299 |
| 043 | 22 | PA | | | 5-0 | 33-22-42 | D02862 | | 7 | | D06042P | 22 | | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0100
Page 35
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0106 | 286T0106 | | | AFT CABIN LEFT FWD (G) (continued) | | | | | | | | | | | |
| 044 | 22 | | PA | | 5-0 | 33-22-42 | D02862 | | | | L00223 | =G | E | * | 275-299 |
| 045 | 22 | | PA | | 5-0 | 33-22-42 | D02862 | | | | D06042P | | 9 | | 275-299 |
| 046 | 22 | | PA | | 5-0 | 33-22-42 | D02862 | | | | D06042P | | 10 | | 275-299 |
| 047 | 22 | | PA | | 5-0 | 33-22-42 | D02862 | | | 12 | D06042P | | 6 | | 275-299 |
| 048 | 22 | | PA | | 5-0 | 33-22-42 | D02862 | | | 11 | D06042P | | 7 | | 275-299 |
| 051 | 22 | | PA | | 7-0 | 23-42-11 | D05335P | | | 1 | L00197 | =P | \$ | | 275-299 |
| 052 | 22 | | PA | | 7-0 | 23-34-13 | D05335P | | | 2 | L00583 | =P | \$ | | 275-299 |
| 053 | 22 | | PA | | 7-0 | 33-25-11 | D05335P | | | 3 | L00569 | =P | \$ | | 275-299 |
| 054 | 20 | | PA | | 7-0 | 23-42-11 | D05335P | | | 4 | L00197 | =G | \$ | | 275-299 |
| 056 | 22 | | PA | | 3-0 | 33-22-42 | SM00011 | | | | L00223 | =4 | C | | 275-299 |
| 057 | 22 | | PA | | 3-0 | 33-22-42 | SM00010 | | | | L00223 | =3 | C | | 275-299 |
| L-A | | | | | 0-0 | 33-22-42 | L00225 | | BLK | | D02862 | | 9 | | 275-299 |
| L-B | | | | | 0-0 | 33-22-42 | L00225 | | BLK | | D02862 | | 10 | | 275-299 |
| L-C | | | | | 0-0 | 33-22-42 | L00225 | | WHT | | D06042P | | 14 | | 275-299 |
| L-D | | | | | 0-0 | 33-22-42 | L00225 | | WHT | | D06042P | | 15 | | 275-299 |
| N-A | | | | | 0-0 | 33-22-42 | L00227 | | BLK | | D06042P | | 2 | | 275-299 |
| N-B | | | | | 0-0 | 33-22-42 | L00227 | | BLK | | D06042P | | 1 | | 275-299 |
| N-C | | | | | 0-0 | 33-22-42 | L00227 | | WHT | | D06042P | | 5 | | 275-299 |
| N-D | | | | | 0-0 | 33-22-42 | L00227 | | WHT | | D06042P | | 4 | | 275-299 |
| W0107 | 286T0107 | | | E1-4 L,SHELF | | | | | | | | | | | |
| 003 | 24 | | PK | | 5-0 | 34-22-38 | D05585P | | | 42 | TB0127F | A064 | 2 | | ALL |
| 016 | 24 | | PV | AP | 4-0 | 34-22-36 | D04205P | | | 1 | TB0127F | A117 | 2 | | ALL |
| 016Z | | | | AP | 0-0 | 34-22-36 | D04205P | | DED | | TB0127F | DED | | | ALL |
| 019 | 24 | | PK | | 4-0 | 34-22-38 | D04901P | | | 1 | TB0127Y | A119 | BJ | | ALL |
| 025 | 24 | | PK | | 5-0 | 34-22-37 | D05585P | | | 1 | TB0127Y | A120 | BJ | | ALL |
| 026 | 24 | | PK | | 5-0 | 34-22-37 | D05585P | | | 2 | TB0127Y | C120 | BJ | | ALL |
| 027 | 24 | | PK | | 5-0 | 34-22-37 | D05585P | | | 3 | TB0127F | A121 | 2 | | ALL |
| 028 | 24 | | PK | | 5-0 | 34-22-37 | D05585P | | | 4 | TB0127F | C121 | 2 | | ALL |
| 044 | 24 | | PK | | 3-0 | 22-15-12 | D05605P | | | 16 | D05607J | | 10 | | ALL |
| 045 | 24 | | PK | | 4-0 | 22-15-12 | D05605P | | | 14 | TB0127F | A137 | 2 | | ALL |
| 046 | 22 | | PA | | 4-0 | 22-14-31 | D05605P | | | 15 | TB0127F | C137 | 2 | | ALL |
| 049 | 24 | | PK | | 4-0 | 22-14-11 | D05605P | | | 31 | TB0127H | 62 | 2 | | ALL |
| 051 | 24 | | PK | | 4-0 | 22-14-11 | D05605P | | | 33 | TB0127H | 58 | 2 | | ALL |
| 052 | 24 | | PK | | 5-0 | 22-41-13 | D04901P | | | 2 | TB0127F | A130 | 2 | | ALL |
| 053 | 24 | | PK | | 4-0 | 22-14-31 | D05605P | | | 17 | TB0127F | C138 | 2 | | ALL |
| 059 | 24 | | PK | | 4-0 | 22-11-12 | D05605P | | | 29 | TB0127G | 45 | 2 | | ALL |
| 060 | 24 | | PK | | 4-0 | 22-11-12 | D05605P | | | 30 | TB0127G | 39 | 2 | | ALL |
| 062 | 22 | | PA | | 4-0 | 34-45-14 | D05605P | | | 25 | TB0127X | C012 | BJ | | 157, 167-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 36

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0107 | 286T0107 | | | E1-4 L,SHELF (continued) | | | | | | | | | | | |
| 063 | 22 | | PA | | 4-0 | 34-45-14 | D05605P | | 26 | | TB0127X | D012 | BJ | | 157, 167-199, 277-299 |
| 078 | 22 | | PA | | 5-0 | 78-36-11 | D20164A | | A09 | | D07160P | 1 | | | ALL |
| 079 | 24 | | PK | | 4-0 | 22-15-12 | D05605P | | 21 | | TB0127F | A139 | 2 | | ALL |
| 080 | 22 | | PA | | 5-0 | 78-36-11 | D20164A | | K03 | | D07160P | 2 | | | ALL |
| 081 | 22 | | PA | | 5-0 | 78-36-11 | D20164A | | A05 | | D07160P | 3 | | | ALL |
| 082 | 22 | | PA | | 5-0 | 78-36-11 | D20164A | | F13 | | D07160P | 4 | | | ALL |
| 083 | 22 | | PA | | 5-0 | 78-36-11 | D20164A | | K11 | | D07160P | 8 | | | ALL |
| 084 | 22 | | PA | | 5-0 | 78-36-11 | D20164A | | K07 | | D07160P | 7 | | | ALL |
| 085 | 22 | | PA | | 5-0 | 78-36-11 | D20164A | | F01 | | D07160P | 6 | | | ALL |
| 086 | 24 | | PK | | 5-0 | 22-41-11 | D05585P | | 38 | | TB0127F | A125 | 2 | | ALL |
| 087 | 22 | | PA | | 5-0 | 78-36-11 | D20164A | | A13 | | D07160P | 9 | | | ALL |
| 088 | 22 | | PA | | 4-0 | 78-36-11 | D20164A | | F09 | | GDX0007 | D.. | 2 | | ALL |
| 089 | 22 | | PA | | 4-0 | 78-36-11 | D20164A | | F05 | | GDX0007 | D.. | 2 | | ALL |
| 090 | 22 | | PA | | 4-0 | 78-36-11 | D20164A | | K15 | | GDX0007 | S.. | 2 | | ALL |
| 091 | 22 | | PA | | 5-0 | 78-36-11 | D20164A | | A01 | | D07160P | 5 | | | ALL |
| 107 | 24 | | PK | | 5-0 | SPARE | D05585P | | 5 | | TB0127F | C121 | # | | 150-199 |
| 201B | 24 | | PW | IA | 5-0 | 34-22-35 | D05585P | | 16 | | TB0127F | C123 | 2 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-22-35 | D05585P | | 15 | | TB0127F | A123 | 2 | | ALL |
| 201Z | | | | IA | 0-0 | 34-22-35 | D05585P | | 17 | | GDY0005 | S.. | 2 | | ALL |
| 202B | 24 | | PL | IB | 5-0 | 23-51-13 | D05605P | | 28 | | TB0127F | C074 | 2 | | ALL |
| 202R | 24 | | PL | IB | 0-0 | 23-51-13 | D05605P | | 27 | | TB0127F | A074 | 2 | | ALL |
| 203B | 24 | | PW | IC | 5-0 | 34-22-38 | D05655P | | 11 | | TB0127F | C017 | 2 | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 34-22-38 | D05655P | | 10 | | TB0127F | A017 | 2 | | ALL |
| 203Z | | | | IC | 0-0 | 34-22-38 | D05655P | | 12 | | GDY0002 | S.. | 2 | | ALL |
| 204B | 24 | | PW | ID | 4-0 | 34-22-39 | D05607J | | 12 | | TB0127F | C101 | 2 | | ALL |
| 204R | 24 | | PW | ID | 0-0 | 34-22-39 | D05607J | | 11 | | TB0127F | A101 | 2 | | ALL |
| 204Z | | | | ID | 0-0 | 34-22-39 | D05607J | | 13 | | GDY0001 | S.. | 2 | | ALL |
| 205B | 24 | | PW | IE | 5-0 | 34-22-39 | D05655P | | 8 | | TB0127F | C103 | 2 | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 34-22-39 | D05655P | | 7 | | TB0127F | A103 | 2 | | ALL |
| 205Z | | | | IE | 0-0 | 34-22-39 | D05655P | | 9 | | GDY0001 | S.. | 2 | | ALL |
| 206B | 24 | | PW | IF | 5-0 | 34-22-13 | D05585P | | 22 | | TB0127G | 108 | 2 | | ALL |
| 206R | 24 | | PW | IF | 0-0 | 34-22-13 | D05585P | | 21 | | TB0127G | 107 | 2 | | ALL |
| 206Z | | | | IF | 0-0 | 34-22-13 | D05585P | | 23 | | GDY0001 | S.. | 2 | | ALL |
| 207B | 24 | | PW | IG | 5-0 | 34-22-13 | D05585P | | 29 | | TB0127G | 143 | 2 | | ALL |
| 207R | 24 | | PW | IG | 0-0 | 34-22-13 | D05585P | | 28 | | TB0127G | 142 | 2 | | ALL |
| 207Z | | | | IG | 0-0 | 34-22-13 | D05585P | | 30 | | GDY0007 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 207Z | | | | IG | 0-0 | 34-22-13 | D05585P | | 30 | | GDY0008 | S.. | 2 | | 150-151 |
| 208B | 24 | | PW | IH | 5-0 | 34-22-13 | D05585P | | 32 | | TB0127G | 112 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 37

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0107 | 286T0107 | | | E1-4 L,SHELF (continued) | | | | | | | | | | | | |
| 208R | 24 | PW | IH | 0-0 | 34-22-13 | D05585P | | 31 | | | TB0127G | 111 | 2 | | ALL | |
| 208Z | | | IH | 0-0 | 34-22-13 | D05585P | | 33 | | | GDY0001 | S.. | 2 | | ALL | |
| 209B | 24 | PW | II | 5-0 | 34-22-38 | D05585P | | 25 | | | TB0127X | B066 | BJ | | ALL | |
| 209R | 24 | PW | II | 0-0 | 34-22-38 | D05585P | | 24 | | | TB0127X | A066 | BJ | | ALL | |
| 209Z | | | II | 0-0 | 34-22-38 | D05585P | | 26 | | | GDY0010 | S.. | 2 | | 050-099, 152-199, 275-299 | |
| 209Z | | | II | 0-0 | 34-22-38 | D05585P | | 26 | | | GDY0011 | S.. | 2 | | 150-151 | |
| 210B | 24 | PW | IJ | 5-0 | 22-41-12 | D05585P | | 40 | | | TB0127F | C156 | 2 | | ALL | |
| 210R | 24 | PW | IJ | 0-0 | 22-41-12 | D05585P | | 39 | | | TB0127F | A156 | 2 | | ALL | |
| 210Z | | | IJ | 0-0 | 22-41-12 | D05585P | | 41 | | | GDY0009 | S.. | 2 | | ALL | |
| 213B | 24 | PW | IM | 4-0 | 22-12-31 | D05605P | | 9 | | | TB0127G | 141 | 2 | | ALL | |
| 213R | 24 | PW | IM | 0-0 | 22-12-31 | D05605P | | 8 | | | TB0127G | 140 | 2 | | ALL | |
| 213Z | | | IM | 0-0 | 22-12-31 | D05605P | | 10 | | | GDY0007 | S.. | 2 | | ALL | |
| 215B | 24 | PW | IO | 5-0 | 22-12-11 | D05605P | | 2 | | | TB0127G | 132 | 2 | | ALL | |
| 215R | 24 | PW | IO | 0-0 | 22-12-11 | D05605P | | 3 | | | TB0127G | 131 | 2 | | ALL | |
| 215Z | | | IO | 0-0 | 22-12-11 | D05605P | | 4 | | | GDY0006 | S.. | 2 | | ALL | |
| 217B | 24 | PW | IQ | 4-0 | 22-12-31 | D05605P | | 6 | | | TB0127F | C134 | 2 | | ALL | |
| 217R | 24 | PW | IQ | 0-0 | 22-12-31 | D05605P | | 5 | | | TB0127F | A134 | 2 | | ALL | |
| 217Z | | | IQ | 0-0 | 22-12-31 | D05605P | | 7 | | | GDY0006 | S.. | 2 | | ALL | |
| 219B | 24 | PW | IS | 4-0 | 22-12-11 | D05607J | | 2 | | | TB0127G | 132 | 2 | | ALL | |
| 219R | 24 | PW | IS | 0-0 | 22-12-11 | D05607J | | 1 | | | TB0127G | 131 | 2 | | ALL | |
| 219Z | | | IS | 0-0 | 22-12-11 | D05607J | | 3 | | | GDY0006 | S.. | 2 | | ALL | |
| 223B | 24 | PW | IW | 4-0 | 22-13-11 | D05605P | | 12 | | | TB0127F | C135 | 2 | | ALL | |
| 223R | 24 | PW | IW | 0-0 | 22-13-11 | D05605P | | 11 | | | TB0127F | A135 | 2 | | ALL | |
| 223Z | | | IW | 0-0 | 22-13-11 | D05605P | | 13 | | | GDY0006 | S.. | 2 | | ALL | |
| 230B | 24 | PW | JE | 4-0 | 22-15-11 | D05605P | | 19 | | | TB0127F | C133 | 2 | | ALL | |
| 230R | 24 | PW | JE | 0-0 | 22-15-11 | D05605P | | 18 | | | TB0127F | A133 | 2 | | ALL | |
| 230Z | | | JE | 0-0 | 22-15-11 | D05605P | | 20 | | | GDY0006 | S.. | 2 | | ALL | |
| 232B | 24 | PW | JG | 4-0 | 34-45-14 | TB0127F | | C129 | 2 | | D05605P | 23 | | | 050-099, 153-199, 277-299 | |
| 232B | 24 | PW | JG | 4-0 | 34-45-14 | TB0127F | | C136 | 2 | | D05605P | 23 | | | 150-152 | |
| 232R | 24 | PW | JG | 0-0 | 34-45-14 | TB0127F | | A129 | 2 | | D05605P | 22 | | | 050-099, 153-199, 277-299 | |
| 232R | 24 | PW | JG | 0-0 | 34-45-14 | TB0127F | | A136 | 2 | | D05605P | 22 | | | 150-152 | |
| 232Z | | | JG | 0-0 | 34-45-14 | GDY0006 | | S.. | 2 | | D05605P | 24 | | | 050-099, 150-199, 277-299 | |
| 236B | 24 | PW | JK | 4-0 | 34-45-14 | D05605P | | 41 | | | TB0127X | B012 | BJ | | 157, 167-199, 277-299 | |
| 236R | 24 | PW | JK | 0-0 | 34-45-14 | D05605P | | 40 | | | TB0127X | A012 | BJ | | 157, 167-199, 277-299 | |
| 236Z | | | JK | 0-0 | 34-45-14 | D05605P | | 42 | | | GDY0002 | S.. | 2 | | 157, 167-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 38

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0107 | 286T0107 | | | E1-4 L,SHELF (continued) | | | | | | | | | | | |
| 239B | 24 | PW | JN | 5-0 | 34-22-38 | D05655P | | 2 | | | TB0127F | C115 | 2 | | ALL |
| 239R | 24 | PW | JN | 0-0 | 34-22-38 | D05655P | | 1 | | | TB0127F | A115 | 2 | | ALL |
| 239Z | | | JN | 0-0 | 34-22-38 | D05655P | | 3 | | | GDY0002 | S.. | 2 | | ALL |
| 248B | 24 | PW | JW | 5-0 | 34-22-39 | D05655P | | 5 | | | TB0127F | C122 | 2 | | ALL |
| 248R | 24 | PW | JW | 0-0 | 34-22-39 | D05655P | | 4 | | | TB0127F | A122 | 2 | | ALL |
| 248Z | | | JW | 0-0 | 34-22-39 | D05655P | | 6 | | | GDY0005 | S.. | 2 | | ALL |
| 250B | 24 | PW | JY | 5-0 | 34-22-39 | D05585P | | 7 | | | TB0127F | C126 | 2 | | ALL |
| 250R | 24 | PW | JY | 0-0 | 34-22-39 | D05585P | | 6 | | | TB0127F | A126 | 2 | | ALL |
| 250Z | | | JY | 0-0 | 34-22-39 | D05585P | | 8 | | | GDY0005 | S.. | 2 | | ALL |
| 251B | 24 | PW | KA | 5-0 | 34-22-39 | D05585P | | 10 | | | TB0127F | C127 | 2 | | ALL |
| 251R | 24 | PW | KA | 0-0 | 34-22-39 | D05585P | | 9 | | | TB0127F | A127 | 2 | | ALL |
| 251Z | | | KA | 0-0 | 34-22-39 | D05585P | | 11 | | | GDY0005 | S.. | 2 | | ALL |
| 255B | 24 | PW | KE | 5-0 | 34-22-38 | D05585P | | 13 | | | TB0127X | D066 | BJ | | ALL |
| 255R | 24 | PW | KE | 0-0 | 34-22-38 | D05585P | | 12 | | | TB0127X | C066 | BJ | | ALL |
| 255Z | | | KE | 0-0 | 34-22-38 | D05585P | | 14 | | | GDY0010 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 255Z | | | KE | 0-0 | 34-22-38 | D05585P | | 14 | | | GDY0011 | S.. | 2 | | 150-151 |
| 256W | 24 | 7K | KF | 4-0 | 34-43-11 | D05585P | | 18 | | | TB0209R | A007 | 2 | | ALL |
| 256WB | 24 | 7K | KF | 0-0 | 34-43-11 | D05585P | | 19 | | | TB0209R | C007 | 2 | | ALL |
| 256Z | | | KF | 0-0 | 34-43-11 | D05585P | | 20 | | | GDZ0001 | S.. | 2 | | ALL |
| 259W | 24 | 7K | KI | 3-0 | 34-43-21 | D05607J | | 5 | | | TB0209R | A008 | 2 | | ALL |
| 259WB | 24 | 7K | KI | 0-0 | 34-43-21 | D05607J | | 4 | | | TB0209R | C008 | 2 | | ALL |
| 259Z | | | KI | 0-0 | 34-43-21 | D05607J | | 6 | | | TB0209R | | | KI | ALL |
| 604 | 22 | PA | | 4-0 | 34-22-36 | D05607J | | 14 | | | TB0127F | A007 | 2 | | ALL |
| 9001B | 24 | PW | B | 5-0 | 34-22-39 | TB0127G | | 16 | 2 | | D05607J | 19 | | | 150, 152-199, 275-299 |
| 9001R | 24 | PW | B | 0-0 | 34-22-39 | TB0127G | | 15 | 2 | | D05607J | 18 | | | 150, 152-199, 275-299 |
| 901Z | | | B | 0-0 | 34-22-39 | GDY0002 | | S.. | 2 | | D05607J | 20 | | | 150, 152-199, 275-299 |
| FRB | | | | 0-3 | 34-43-21 | TB0209R | | | | KI | GDZ0001 | S.. | 2 | | ALL |
| W0108 | 286T0108 | | | AFT CABIN RIGHT FWD (H) | | | | | | | | | | | |
| 014 | 22 | PA | | 5-0 | 33-22-42 | D02864 | | 8 | | | L00224 | =G | E | * | 275-299 |
| 018 | 22 | PA | | 3-0 | 33-22-42 | D06052P | | 6 | | | SP01152 | | 9 | | 275-299 |
| 019 | 22 | PA | | 3-0 | 33-22-42 | D06052P | | 7 | | | SP01150 | | 9 | | 275-299 |
| 020 | 22 | PA | | 3-0 | 33-22-42 | D02864 | | 11 | | | SP01150 | | 9 | | 275-299 |
| 021 | 22 | PA | | 3-0 | 33-22-42 | D02864 | | 12 | | | SP01152 | | 9 | | 275-299 |
| 023 | 22 | PA | | 5-0 | 33-22-42 | D06052P | | 10 | | | L00224 | =G | E | * | 275-299 |
| 024 | 22 | PA | | 5-0 | 33-22-42 | D06052P | | 11 | | | L00224 | =1 | C | | 275-299 |
| 025 | 22 | PA | | 5-0 | 33-22-42 | D06052P | | 12 | | | L00224 | =2 | C | | 275-299 |
| 026 | 22 | PA | | 5-0 | 33-22-42 | D06052P | | 8 | | | L00224 | =3 | C | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0100
Page 39
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0108 | 286T0108 | | | AFT CABIN RIGHT FWD (H) (continued) | | | | | | | | | | | |
| 027 | 22 | | PA | | 5-0 | 33-22-42 | D06052P | | | | L00224 | =4 | C | | 275-299 |
| 028 | 22 | | PA | | 3-0 | 33-22-42 | D06052P | | | | SP01164 | | 9 | | 275-299 |
| 029 | 22 | | PA | | 3-0 | 33-22-42 | D06052P | | | | SP01162 | | 9 | | 275-299 |
| 033 | 22 | | PA | | 3-0 | 33-22-42 | D06052P | | | | SP01164 | | 9 | | 275-299 |
| 034 | 22 | | PA | | 3-0 | 33-22-42 | D06052P | | | | SP01162 | | 9 | | 275-299 |
| 035 | 22 | | PA | | 5-0 | 33-22-42 | D02864 | | | | D06052P | | 23 | | 275-299 |
| 036 | 22 | | PA | | 5-0 | 33-22-42 | D02864 | | | | D06052P | | 3 | | 275-299 |
| 037 | 22 | | PA | | 5-0 | 33-22-42 | D02864 | | | | D06052P | | 2 | | 275-299 |
| 038 | 22 | | PA | | 5-0 | 33-22-42 | D02864 | | | | D06052P | | 20 | | 275-299 |
| 051 | 22 | | PA | | 7-0 | 23-42-11 | D05337P | | | | L00198 | =P | \$ | | 275-299 |
| 052 | 22 | | PA | | 7-0 | 23-34-13 | D05337P | | | | L00584 | =P | \$ | | 275-299 |
| 053 | 22 | | PA | | 7-0 | 33-25-11 | D05337P | | | | L00568 | =P | \$ | | 275-299 |
| 054 | 20 | | PA | | 7-0 | 23-42-11 | D05337P | | | | L00198 | =G | \$ | | 275-299 |
| I-A | | | | | 0-0 | 33-22-42 | L00228 | | BLK | | D02864 | | 2 | | 275-299 |
| I-B | | | | | 0-0 | 33-22-42 | L00228 | | BLK | | D02864 | | 3 | | 275-299 |
| I-C | | | | | 0-0 | 33-22-42 | L00228 | | WHT | | SP01152 | | 9 | | 275-299 |
| I-D | | | | | 0-0 | 33-22-42 | L00228 | | WHT | | SP01150 | | 9 | | 275-299 |
| K-A | | | | | 0-0 | 33-22-42 | L00226 | | BLK | | D06052P | | 14 | | 275-299 |
| K-B | | | | | 0-0 | 33-22-42 | L00226 | | BLK | | D06052P | | 15 | | 275-299 |
| K-C | | | | | 0-0 | 33-22-42 | L00226 | | WHT | | SP01162 | | 9 | | 275-299 |
| K-D | | | | | 0-0 | 33-22-42 | L00226 | | WHT | | SP01164 | | 9 | | 275-299 |
| W0109 | 286T0109 | | | E1-5 SHELF L | | | | | | | | | | | |
| 002 | 24 | | PK | | 3-1 | 34-46-12 | D04853P | | | | D00435B | A01 | | | ALL |
| 004 | 22 | | PA | | 3-7 | 34-22-16 | D04525P | | | | TB0119G | 110 | 2 | | ALL |
| 015 | 22 | | PA | | 3-0 | 34-22-23 | D04525P | | | | TB0119F | C021 | 2 | | ALL |
| 020 | 24 | | PK | | 4-0 | 27-32-11 | D05817P | | | | D05525P | 1 | | | ALL |
| 023 | 24 | | PK | | 4-3 | 31-31-26 | D05523P | | | | D04853P | 26 | | | ALL |
| 024 | 24 | | PK | | 4-3 | 31-31-26 | TB0119G | | | 2 | D04853P | 27 | | | ALL |
| 025 | 22 | | PA | | 5-3 | 34-46-12 | D05523P | | | | TB0119G | 180 | 2 | | ALL |
| 026 | 20 | | PA | | 4-9 | 21-61-51 | D13460C | | | | GD0001 | A.. | 2 | | ALL |
| 027 | 18 | | PA | | 3-5 | 21-61-51 | D13460C | | | | TB0119G | 79 | 2 | | 150-199, 275-299 |
| 028 | 24 | | PV | BC | 5-4 | 21-61-51 | D06732P | | | | D13460C | 2 | | | 050-099 |
| 028 | 24 | | PV | BC | 4-10 | 21-61-51 | D06732P | | | | TB0119G | 79 | 2 | | 150-199, 275-299 |
| 028Z | | | | BC | 0-0 | 21-61-51 | D06732P | | | DED | D13460C | DED | | | 050-099 |
| 028Z | | | | BC | 0-0 | 21-61-51 | D06732P | | | DED | TB0119G | DED | | | 150-199, 275-299 |
| 030 | 24 | | PK | | 5-0 | 21-61-51 | D13460B | | | C03 | D05525P | 16 | | | 050-099, 275-299 |
| 030 | 24 | | PK | | 5-0 | 21-61-51 | D13460B | | | C03 | D05525P | 3 | | | 150-199 |
| 031 | 24 | | PK | | 3-6 | 21-61-61 | D06732P | | | | D06734P | 15 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 40

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|---------------------------------|-------|-------------|------|----------|---------|-------|------|------|---------|-------|------|------|--------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0109 | 286T0109 | E1-5 SHELF L (continued) | | | | | | | | | | | | | |
| 032 | 24 | | PK | | 6-4 | 21-61-61 | D05817P | | 3 | | D13460B | B12 | | | ALL |
| 033 | 24 | | PK | | 6-4 | 21-61-61 | D05817P | | 6 | | D13460B | B11 | | | ALL |
| 034 | 24 | | PK | | 6-4 | 21-61-61 | D05817P | | 16 | | D13460B | B09 | | | ALL |
| 035 | 24 | | PK | | 6-4 | 21-61-71 | D13460B | | C09 | | D05817P | 17 | | | ALL |
| 036 | 24 | | PK | | 6-4 | 21-61-71 | D13460B | | C12 | | D05817P | 18 | | | ALL |
| 037 | 24 | | PK | | 6-4 | 21-61-71 | D13460B | | C11 | | D05817P | 19 | | | ALL |
| 038 | 24 | | PK | | 3-6 | 21-61-71 | D06732P | | 18 | | D06734P | 22 | | | ALL |
| 039 | 24 | | PK | | 3-9 | 21-61-71 | D05817P | | 22 | | D06734P | 23 | | | ALL |
| 040 | 24 | | PK | | 3-9 | 21-61-71 | D05817P | | 23 | | D06734P | 24 | | | ALL |
| 041 | 24 | | PK | | 4-1 | 21-26-31 | D06732P | | 20 | | D13560A | B03 | | | ALL |
| 042 | 24 | | PK | | 4-6 | 21-26-31 | D06732P | | 21 | | TB0119G | 59 | 2 | | ALL |
| 043 | 24 | | PK | | 3-4 | 21-26-31 | D06734P | | 25 | | D13560A | H03 | | | ALL |
| 044 | 24 | | PK | | 3-4 | 21-26-31 | D06734P | | 26 | | D13560A | E02 | | | ALL |
| 045 | 24 | | PK | | 3-4 | 21-26-31 | D06734P | | 27 | | D13560A | H02 | | | ALL |
| 046 | 24 | | PK | | 3-4 | 21-26-31 | D06734P | | 28 | | D13560B | G03 | | | ALL |
| 047 | 24 | | PK | | 3-4 | 21-28-11 | D06734P | | 29 | | D13560A | F04 | | | ALL |
| 048 | 24 | | PK | | 3-4 | 21-28-11 | D06734P | | 30 | | D13560A | F05 | | | ALL |
| 049 | 24 | | PK | | 3-4 | 21-28-11 | D06734P | | 31 | | D13560A | D02 | | | ALL |
| 050 | 24 | | PK | | 3-4 | 21-28-11 | D06734P | | 32 | | D13560A | D03 | | | ALL |
| 051 | 24 | | PK | | 3-4 | 21-28-11 | D06734P | | 33 | | D13560A | E04 | | | ALL |
| 054 | 24 | | PK | | 3-4 | 21-28-11 | D06734P | | 34 | | D13560A | E03 | | | ALL |
| 056 | 22 | | PA | | 3-2 | 22-14-21 | D04853P | | 10 | | TB0119F | A126 | 2 | | ALL |
| 057 | 24 | | PK | | 4-1 | 21-28-11 | D06732P | | 22 | | D13560A | B02 | | | ALL |
| 058 | 24 | | PK | | 3-4 | 21-28-11 | D06734P | | 35 | | D13560B | H04 | | | ALL |
| 059 | 24 | | PK | | 3-4 | 21-28-11 | D06734P | | 36 | | D13560B | F02 | | | ALL |
| 060 | 24 | | PK | | 3-4 | 21-28-11 | D06734P | | 37 | | D13560B | F04 | | | ALL |
| 061 | 24 | | PK | | 4-8 | 21-43-11 | TB0119Y | C183 | BJ | | D06734P | 52 | | | ALL |
| 062 | 24 | | PK | | 3-4 | 21-43-11 | D13560A | | F02 | | D06734P | 53 | | | ALL |
| 063 | 24 | | PK | | 3-4 | 21-43-11 | D13560A | | F03 | | D06734P | 54 | | | ALL |
| 064 | 24 | | PK | | 4-1 | 22-14-11 | D05523P | | 8 | | TB0119H | 148 | 2 | | ALL |
| 065 | 24 | | PK | | 2-9 | 22-15-12 | D05607P | | 10 | | TB0119F | C128 | 2 | | ALL |
| 066 | 24 | | PK | | 3-4 | 21-43-11 | D13560A | | G04 | | D06734P | 55 | | | ALL |
| 067 | 24 | | PK | | 4-1 | 21-43-11 | D13560A | | C02 | | D06732P | 30 | | | ALL |
| 068 | 24 | | PK | | 4-7 | 22-14-11 | D05523P | | 7 | | TB0119H | 51 | 2 | | ALL |
| 069 | 24 | | PK | | 4-1 | 21-43-11 | D13560B | | H02 | | D06732P | 29 | | | ALL |
| 070 | 24 | | PK | | 3-6 | 22-14-11 | D04853P | | 6 | | TB0119H | 51 | 2 | | ALL |
| 071 | 24 | | PK | | 4-0 | 22-14-11 | D04853P | | 8 | | TB0119H | 57 | 2 | | ALL |
| 072 | 24 | | PK | | 5-0 | 22-14-11 | D05523P | | 9 | | TB0119H | 57 | 2 | | ALL |
| 073 | 24 | | PK | | 3-6 | 22-14-11 | D04853P | | 9 | | TB0119H | 49 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0100
 Page 41
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0109 | 286T0109 | | | E1-5 SHELF L (continued) | | | | | | | | | | | | |
| 074 | 24 | | PK | 3-6 | 21-28-11 | TB0119Y | A183 | BJ | | D13560B | D03 | | | ALL | | |
| 075 | 24 | | PK | 2-10 | 21-51-11 | TB0119D | C196 | 2 | | TB0119Y | A183 | BJ | | ALL | | |
| 076 | 24 | | PK | 4-8 | 21-28-11 | D06734P | 43 | | | TB0119Y | A183 | BJ | | ALL | | |
| 077 | 24 | | PK | 3-4 | 21-51-11 | D06734P | 2 | | | D13560B | D02 | | | ALL | | |
| 078 | 24 | | PK | 3-4 | 21-51-11 | D06734P | 50 | | | D13560B | F05 | | | ALL | | |
| 079 | 24 | | PK | 3-3 | 21-51-11 | D06732P | 26 | | | TB0119Y | A122 | BJ | | 050-099, 155-199, 277-299 | | |
| 079 | 24 | | PK | 6-1 | 21-51-11 | D06732P | 26 | | | TB0119Y | A096 | BJ | | 150-154, 275-276 | | |
| 080 | 24 | | PK | 4-0 | 21-51-11 | D06732P | 27 | | | D13560B | G05 | | | ALL | | |
| 081 | 24 | | PK | 3-3 | 21-51-11 | TB0119Y | A122 | BJ | | D13560B | H05 | | | 050-099, 155-199, 277-299 | | |
| 081 | 24 | | PK | 4-0 | 21-51-11 | TB0119Y | A096 | BJ | | D13560B | H05 | | | 150-154, 275-276 | | |
| 082 | 24 | | PK | 3-6 | 22-14-11 | D04853P | 11 | | | TB0119H | 148 | 2 | | ALL | | |
| 083 | 24 | | PK | 3-3 | 22-15-12 | D04853P | 2 | | | TB0119F | A123 | 2 | | ALL | | |
| 084 | 24 | | PK | 4-8 | 21-51-11 | D06734P | 41 | | | TB0119Y | CAP | Y | | 050, 150-154, 275-276 | | |
| 085 | 24 | | PK | 4-8 | 21-51-11 | D06734P | 44 | | | TB0119Y | C186 | BJ | | ALL | | |
| 086 | 24 | | PK | 4-8 | 21-51-11 | D06734P | 42 | | | TB0119Y | C184 | BJ | | ALL | | |
| 089 | 24 | | PK | 3-6 | 21-51-11 | TB0119Y | A186 | BJ | | D13560B | F08 | | | 050, 150-154, 275-276 | | |
| 090 | 24 | | PK | 3-6 | 21-51-11 | TB0119Y | C186 | BJ | | D13560B | D08 | | | ALL | | |
| 093 | 24 | | PK | 3-6 | 22-41-11 | D04525P | 17 | | | TB0119F | A128 | 2 | | ALL | | |
| 095 | 24 | | PK | 3-0 | 34-16-11 | D04853P | 32 | | | D05525P | 3 | | | 275-299 | | |
| 096 | 24 | | PK | 3-0 | 34-16-11 | D04853P | 33 | | | D05525P | 4 | | | 275-299 | | |
| 097 | 24 | | PK | 3-6 | 21-51-11 | TB0119Y | C184 | BJ | | D13560B | C08 | | | ALL | | |
| 098 | 24 | | PK | 3-8 | 21-51-11 | TB0119Y | C189 | BJ | | D13560B | H08 | | | ALL | | |
| 099 | 24 | | PK | 3-4 | 21-51-11 | D06734P | 45 | | | D13560A | E09 | | | ALL | | |
| 101 | 24 | | PK | 3-6 | 22-14-31 | D04853P | 30 | | | TB0119H | 49 | 2 | | ALL | | |
| 102 | 24 | | PK | 3-0 | 31-51-21 | D05525P | 2 | | | TB0119H | 139 | 2 | | ALL | | |
| 104 | 22 | | PA | 2-9 | 34-46-12 | D00435A | A10 | | | TB0119H | 119 | 2 | | 050-099, 151 | | |
| 106 | 22 | | PA | 2-9 | 34-46-12 | D00435A | A11 | | | TB0119H | 119 | 2 | | 050-099, 151 | | |
| 107 | 22 | | PA | 5-4 | 34-46-11 | D05257P | 4 | | | TB0119D | C097 | 2 | | 050-099, 150-152, 155-199, 275-299 | | |
| 107 | 22 | | PA | 3-9 | 34-46-11 | D05257P | 4 | | | TB0119D | C097 | 2 | | 153-154 | | |
| 108 | 22 | | PA | 3-6 | 34-46-11 | D00435A | A12 | | | TB0119H | 139 | 2 | | 050-099, 151 | | |
| 109 | 22 | | PA | 2-9 | 34-46-11 | D00435B | A03 | | | TB0119H | 119 | 2 | | 050-099, 151 | | |
| 110 | 24 | | PK | 3-2 | 34-22-16 | D04525P | 8 | | | TB0119H | 139 | 2 | | ALL | | |
| 111 | 22 | | PA | 2-9 | 34-46-12 | D00435A | B10 | | | TB0119H | 119 | 2 | | 151 | | |
| 112 | 20 | | PA | 3-10 | 38-32-11 | D05525P | 5 | | | D05817P | 10 | | | 050-099, 150-199, 277-299 | | |
| 112 | 20 | | PA | 3-10 | SPARE | D05525P | 5 | | | D05817P | 10 | | | 276 | | |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 42

Sep 04/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0109 | 286T0109 | | | E1-5 SHELF L (continued) | | | | | | | | | | | |
| 113 | 22 | | PA | | 2-6 | 21-51-11 | D13560B | H12 | | | GDX0011 | D.. | 2 | | ALL |
| 114 | 22 | | PA | | 2-6 | 21-51-11 | D13560B | H13 | | | GDX0011 | D.. | 2 | | ALL |
| 115 | 22 | | PA | | 2-6 | 21-51-11 | D13560B | H14 | | | GDX0011 | D.. | 2 | | ALL |
| 116 | 24 | | PK | | 3-8 | 21-51-11 | TB0119Y | C122 | BJ | | D13560B | B03 | | | 050-099, 155-199, 277-299 |
| 116 | 24 | | PK | | 3-9 | 21-51-11 | TB0119Y | C096 | BJ | | D13560B | B03 | | | 150-154, 275-276 |
| 117 | 24 | | PK | | 5-6 | 21-51-11 | D06732P | 32 | | | TB0119Y | C184 | BJ | | ALL |
| 118 | 24 | | PK | | 6-0 | 21-51-11 | D06732P | 33 | | | TB0119Y | C189 | BJ | | ALL |
| 119 | 24 | | PK | | 6-0 | 21-51-11 | D06732P | 34 | | | TB0119Y | C189 | BJ | | ALL |
| 120 | 24 | | PK | | 4-0 | 21-51-11 | D06732P | 35 | | | D13560B | D12 | | | ALL |
| 121 | 24 | | PK | | 4-0 | 21-51-11 | D06732P | 36 | | | D13560B | D14 | | | ALL |
| 122 | 24 | | PK | | 4-0 | 21-51-11 | D06732P | 37 | | | D13560B | F14 | | | ALL |
| 123 | 22 | | PQ | EW | 4-6 | 21-51-11 | D06732P | 38 | | | TB0119G | 60 | 2 | | ALL |
| 123Z | | | | EW | 0-0 | 21-51-11 | D06732P | DED | | | TB0119G | DED | | | ALL |
| 124 | 22 | | PA | | 3-8 | 21-51-11 | TB0119Y | A189 | BJ | | D13560B | J12 | | | ALL |
| 125 | 22 | | PA | | 3-8 | 21-51-11 | TB0119Y | A189 | BJ | | D13560B | J13 | | | ALL |
| 126 | 22 | | PA | | 3-8 | 21-51-11 | TB0119Y | A189 | BJ | | D13560B | J14 | | | ALL |
| 128 | 24 | | PK | | 4-0 | 21-51-11 | D06732P | 39 | | | D13560A | F09 | | | ALL |
| 129 | 24 | | PK | | 4-0 | 21-51-11 | D06732P | 40 | | | D13560A | F08 | | | ALL |
| 130 | 24 | | PK | | 4-0 | 21-51-11 | D06732P | 41 | | | D13560A | D09 | | | ALL |
| 131 | 24 | | PK | | 4-0 | 21-51-11 | D06732P | 42 | | | D13560A | D08 | | | ALL |
| 132 | 24 | | PK | | 4-0 | 21-51-11 | D06732P | 43 | | | D13560A | B04 | | | ALL |
| 134 | 20 | | PA | | 2-6 | 21-51-11 | D13560C | 8 | | | GDX0011 | S.. | 2 | | ALL |
| 136 | 24 | | PK | | 4-0 | 21-51-11 | D13560A | B09 | | | D06732P | 44 | | | ALL |
| 137 | 24 | | PK | | 4-0 | 21-51-11 | D13560A | B08 | | | D06732P | 45 | | | ALL |
| 138 | 24 | | PK | | 4-0 | 21-51-11 | D13560A | G08 | | | D06732P | 46 | | | ALL |
| 139 | 24 | | PK | | 4-0 | 21-51-11 | D13560B | J08 | | | D06732P | 47 | | | ALL |
| 140 | 24 | | PK | | 4-0 | 21-51-11 | D13560B | G08 | | | D06732P | 48 | | | ALL |
| 141 | 24 | | PK | | 4-0 | 21-51-11 | D13560A | C08 | | | D06732P | 49 | | | ALL |
| 142 | 24 | | PK | | 4-0 | 21-51-11 | D13560A | C09 | | | D06732P | 50 | | | ALL |
| 143 | 24 | | PK | | 3-7 | 21-51-11 | D13560A | J03 | | | TB0119Y | A185 | BJ | | ALL |
| 144 | 24 | | PK | | 3-6 | 21-51-11 | D13560A | J02 | | | TB0119Y | C185 | BJ | | ALL |
| 145 | 24 | | PK | | 4-0 | 21-51-11 | D13560A | H08 | | | D06732P | 51 | | | ALL |
| 146 | 24 | | PK | | 4-0 | 21-51-11 | D13560A | G09 | | | D06732P | 52 | | | ALL |
| 147 | 24 | | PK | | 4-0 | 21-51-11 | D13560A | E08 | | | D06732P | 53 | | | ALL |
| 148 | 24 | | PK | | 5-6 | 21-51-11 | TB0119Y | A186 | BJ | | D06732P | 54 | | | 050, 150-154, 275-276 |
| 149 | 24 | | PK | | 5-6 | 21-51-11 | TB0119Y | C186 | BJ | | D06732P | 55 | | | ALL |
| 150 | 24 | | PK | | 3-7 | 21-61-81 | D13560B | B02 | | | D13460A | D10 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0100
Page 43
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0109 | 286T0109 | | | E1-5 SHELF L (continued) | | | | | | | | | | | | |
| 151 | 24 | | PK | 5-0 | 21-51-11 | TB0119Y | A122 | BJ | | TB0119D | A196 | 2 | | 050-099, 155-199, 277-299 | | |
| 151 | 24 | | PK | 3-0 | 21-51-11 | TB0119Y | A096 | BJ | | TB0119D | A196 | 2 | | 150-154, 275-276 | | |
| 152 | 24 | | PK | 2-10 | 21-61-81 | TB0119Y | A185 | BJ | | D13460B | A09 | | | ALL | | |
| 153 | 24 | | PK | 3-4 | 21-43-11 | D13560A | G02 | | | D06734P | 51 | | | ALL | | |
| 155 | 24 | | PK | 6-0 | 21-43-11 | TB0119Y | C183 | BJ | | D06754P | 14 | | | ALL | | |
| 156 | 24 | | PK | 4-1 | 21-43-11 | D13560A | G03 | | | D06732P | 31 | | | ALL | | |
| 157 | 24 | | PK | 5-0 | 21-51-11 | TB0119D | C197 | 2 | | TB0119Y | A122 | BJ | | 050-099, 155-199, 277-299 | | |
| 157 | 24 | | PK | 3-0 | 21-51-11 | TB0119D | C197 | 2 | | TB0119Y | A096 | BJ | | 150-154, 275-276 | | |
| 159 | 24 | | PK | 2-11 | 21-61-81 | TB0119Y | C185 | BJ | | D13460B | A05 | | | ALL | | |
| 160 | 24 | | PK | 6-5 | 21-61-81 | D06754P | 10 | | | D13460B | A12 | | | ALL | | |
| 161 | 24 | | PK | 6-5 | 21-61-81 | D06754P | 11 | | | D13460B | A11 | | | ALL | | |
| 162 | 24 | | PK | 4-6 | 21-61-81 | D06752P | 4 | | | D06754P | 8 | | | ALL | | |
| 163 | 22 | | PA | 2-8 | 21-61-81 | D13460A | D14 | | | GDX0011 | D.. | 2 | | ALL | | |
| 164 | 24 | | PK | 5-0 | 21-61-81 | D13460A | D12 | | | TB0119Y | C122 | BJ | | 050-099, 155-199, 277-299 | | |
| 164 | 24 | | PK | 3-0 | 21-61-81 | D13460A | D12 | | | TB0119Y | C096 | BJ | | 150-154, 275-276 | | |
| 165 | 24 | | PK | 6-0 | 21-25-11 | D13560A | J08 | | | D06732P | 24 | | | ALL | | |
| 166 | 24 | | PK | 6-0 | 21-51-11 | D13560A | H09 | | | D06732P | 25 | | | ALL | | |
| 167 | 24 | | PK | 4-8 | 21-51-11 | D13560B | B08 | | | D06734P | 47 | | | ALL | | |
| 168 | 24 | | PK | 5-4 | 21-53-11 | D13560B | F12 | | | D06752P | 6 | | | ALL | | |
| 169 | 20 | | PA | 4-9 | 21-61-51 | D13460C | 3 | | | GDX0001 | S.. | 2 | | ALL | | |
| 170 | 22 | | PA | 4-9 | 21-61-51 | D13460A | C15 | | | GDX0001 | D.. | 2 | | ALL | | |
| 185 | 24 | | PK | 5-0 | 21-51-11 | TB0119D | A197 | 2 | | TB0119Y | C122 | BJ | | 050-099, 155-199, 277-299 | | |
| 185 | 24 | | PK | 3-0 | 21-51-11 | TB0119D | A197 | 2 | | TB0119Y | C096 | BJ | | 150-154, 275-276 | | |
| 195 | 24 | | PK | 4-1 | 73-21-15 | D06752P | 9 | | | D13560B | E08 | | | ALL | | |
| 201B | 24 | | PW IA | 3-0 | 34-22-91 | D05523P | 20 | | | D05609J | 6 | | | ALL | | |
| 201R | 24 | | PW IA | 0-0 | 34-22-91 | D05523P | 19 | | | D05609J | 5 | | | ALL | | |
| 201Z | | | IA | 0-0 | 34-22-91 | D05523P | 21 | | | D05609J | 7 | | | ALL | | |
| 202B | 24 | | PW IB | 3-4 | 34-22-28 | D04517P | 10 | | | TB0119F | C020 | 2 | | ALL | | |
| 202R | 24 | | PW IB | 0-0 | 34-22-28 | D04517P | 9 | | | TB0119F | A020 | 2 | | ALL | | |
| 202Z | | | IB | 0-0 | 34-22-28 | D04517P | 11 | | | GDY0002 | S.. | 2 | | ALL | | |
| 203B | 24 | | PW IC | 3-6 | 27-32-11 | D05525P | 11 | | | TB0119H | 108 | 2 | | ALL | | |
| 203R | 24 | | PW IC | 0-0 | 27-32-11 | D05525P | 10 | | | TB0119H | 106 | 2 | | ALL | | |
| 203Z | | | IC | 0-0 | 27-32-11 | D05525P | 12 | | | GDY0001 | S.. | 2 | | 050-099, 275-299 | | |
| 203Z | | | IC | 0-0 | 27-32-11 | D05525P | 12 | | | GDY0002 | S.. | 2 | | 150-199 | | |
| 204B | 24 | | PW ID | 3-8 | 27-32-11 | D05525P | 14 | | | D05817P | 13 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 44

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0109 | 286T0109 | | | E1-5 SHELF L (continued) | | | | | | | | | | | |
| 204R | 24 | PW | ID | | 0-0 | 27-32-11 | D05525P | | 13 | | D05817P | | 12 | | ALL |
| 204Z | | | ID | | 0-0 | 27-32-11 | D05525P | | 15 | | D05817P | | 14 | | ALL |
| 206B | 24 | PW | IF | | 3-5 | 34-22-19 | D04525P | | 26 | | TB0119H | | 108 | 2 | ALL |
| 206R | 24 | PW | IF | | 0-0 | 34-22-19 | D04525P | | 25 | | TB0119H | | 106 | 2 | ALL |
| 206Z | | | IF | | 0-0 | 34-22-19 | D04525P | | 27 | | GDY0001 | | S.. | 2 | ALL |
| 207B | 24 | PW | IG | | 4-0 | 34-46-12 | D00435A | | D09 | | TB0119H | | 158 | 2 | ALL |
| 207R | 24 | PW | IG | | 0-0 | 34-46-12 | D00435A | | C09 | | TB0119H | | 156 | 2 | ALL |
| 207Z | | | IG | | 0-0 | 34-46-12 | D00435A | | DED | | GDY0009 | | S.. | 2 | ALL |
| 208B | 24 | PW | IH | | 3-0 | 34-46-12 | D00435B | | D12 | | TB0119H | | 108 | 2 | ALL |
| 208R | 24 | PW | IH | | 0-0 | 34-46-12 | D00435B | | C12 | | TB0119H | | 106 | 2 | ALL |
| 208Z | | | IH | | 0-0 | 34-46-12 | D00435B | | DED | | GDY0001 | | S.. | 2 | 050-099, 275-299 |
| 208Z | | | IH | | 0-0 | 34-46-12 | D00435B | | DED | | GDY0002 | | S.. | 2 | 150-199 |
| 209B | 24 | PW | II | | 3-1 | 34-22-39 | D05607P | | 12 | | TB0119H | | 108 | 2 | ALL |
| 209R | 24 | PW | II | | 0-0 | 34-22-39 | D05607P | | 11 | | TB0119H | | 106 | 2 | ALL |
| 209Z | | | II | | 0-0 | 34-22-39 | D05607P | | 13 | | GDY0001 | | S.. | 2 | ALL |
| 211B | 24 | PW | IK | | 3-3 | 34-46-12 | D04853P | | 16 | | TB0119G | | 134 | 2 | ALL |
| 211R | 24 | PW | IK | | 0-0 | 34-46-12 | D04853P | | 15 | | TB0119G | | 133 | 2 | ALL |
| 211Z | | | IK | | 0-0 | 34-46-12 | D04853P | | 17 | | GDY0006 | | S.. | 2 | ALL |
| 212B | 24 | PW | IL | | 3-10 | 34-61-14 | D05573P | | 11 | | TB0119H | | 63 | 2 | ALL |
| 212R | 24 | PW | IL | | 0-0 | 34-61-14 | D05573P | | 10 | | TB0119H | | 61 | 2 | ALL |
| 212Z | | | IL | | 0-0 | 34-61-14 | D05573P | | 12 | | GDY0010 | | S.. | 2 | ALL |
| 213B | 24 | PL | IM | | 3-7 | 21-61-51 | D13460A | | D07 | | TB0119Y | | C077 | BJ | ALL |
| 213R | 24 | PL | IM | | 0-0 | 21-61-51 | D13460A | | D11 | | TB0119Y | | A077 | BJ | ALL |
| 214B | 24 | PL | IN | | 4-1 | 21-61-51 | D06734P | | 3 | | TB0119Y | | C077 | BJ | ALL |
| 214R | 24 | PL | IN | | 0-0 | 21-61-51 | D06734P | | 4 | | TB0119Y | | A077 | BJ | ALL |
| 215B | 24 | PL | IO | | 4-1 | 21-61-51 | D06734P | | 5 | | TB0119Y | | C077 | BJ | ALL |
| 215R | 24 | PL | IO | | 0-0 | 21-61-51 | D06734P | | 6 | | TB0119Y | | A077 | BJ | ALL |
| 216B | 24 | PL | IP | | 4-7 | 21-61-51 | D13460B | | A01 | | D06734P | | 7 | | ALL |
| 216R | 24 | PL | IP | | 0-0 | 21-61-51 | D13460B | | A02 | | D06734P | | 8 | | ALL |
| 217B | 24 | PL | IQ | | 4-7 | 21-61-51 | D13460B | | A03 | | D06734P | | 9 | | ALL |
| 217R | 24 | PL | IQ | | 0-0 | 21-61-51 | D13460B | | A04 | | D06734P | | 10 | | ALL |
| 218B | 24 | PL | IR | | 4-7 | 21-61-51 | D13460B | | C07 | | D06734P | | 11 | | ALL |
| 218R | 24 | PL | IR | | 0-0 | 21-61-51 | D13460B | | C08 | | D06734P | | 12 | | ALL |
| 219B | 24 | PL | IS | | 4-7 | 21-61-51 | D13460B | | D03 | | D06734P | | 13 | | ALL |
| 219R | 24 | PL | IS | | 0-0 | 21-61-51 | D13460B | | D04 | | D06734P | | 14 | | ALL |
| 220B | 24 | PL | IT | | 5-5 | 21-61-51 | D13460B | | D07 | | D06732P | | 2 | | ALL |
| 220R | 24 | PL | IT | | 0-0 | 21-61-51 | D13460B | | D08 | | D06732P | | 3 | | ALL |
| 221B | 24 | PL | IU | | 6-3 | 21-61-61 | D05817P | | 8 | | D13460B | | B13 | | ALL |
| 221R | 24 | PL | IU | | 0-0 | 21-61-61 | D05817P | | 7 | | D13460B | | B15 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0100
 Page 45
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0109 | 286T0109 | | | E1-5 SHELF L (continued) | | | | | | | | | | | |
| 222B | 24 | PL | IV | 6-0 | 21-61-61 | D06732P | | 7 | | D13460A | B04 | | | ALL | |
| 222R | 24 | PL | IV | 0-0 | 21-61-61 | D06732P | | 8 | | D13460A | B05 | | | ALL | |
| 224B | 24 | PL | IX | 6-0 | 21-61-61 | D06732P | | 9 | | D13460A | B06 | | | ALL | |
| 224R | 24 | PL | IX | 0-0 | 21-61-61 | D06732P | | 10 | | D13460A | B07 | | | ALL | |
| 225B | 24 | PL | IY | 6-0 | 21-61-71 | D13460A | | C04 | | D06732P | 11 | | | ALL | |
| 225R | 24 | PL | IY | 0-0 | 21-61-71 | D13460A | | C05 | | D06732P | 12 | | | ALL | |
| 226B | 24 | PL | JA | 6-0 | 21-61-71 | D13460A | | C06 | | D06732P | 14 | | | ALL | |
| 226R | 24 | PL | JA | 0-0 | 21-61-71 | D13460A | | C07 | | D06732P | 13 | | | ALL | |
| 227B | 24 | PL | JB | 6-3 | 21-61-71 | D13460B | | C13 | | D05817P | 21 | | | ALL | |
| 227R | 24 | PL | JB | 0-0 | 21-61-71 | D13460B | | C15 | | D05817P | 20 | | | ALL | |
| 228B | 24 | PL | JC | 4-0 | 21-28-11 | D06734P | | 40 | | D13560B | B14 | | | ALL | |
| 228R | 24 | PL | JC | 0-0 | 21-28-11 | D06734P | | 39 | | D13560B | B13 | | | ALL | |
| 229B | 24 | PL | JD | 3-0 | 21-61-81 | D13460A | | A06 | | TB0119Y | C087 | BJ | | 050-099, 151-199, 275-299 | |
| 229B | 24 | PL | JD | 6-6 | 21-61-81 | D13460A | | A06 | | D06754P | 1 | | | 150 | |
| 229R | 24 | PL | JD | 0-0 | 21-61-81 | D13460A | | A07 | | TB0119Y | A087 | BJ | | 050-099, 151-199, 275-299 | |
| 229R | 24 | PL | JD | 0-0 | 21-61-81 | D13460A | | A07 | | D06754P | 2 | | | 150 | |
| 230B | 24 | PL | JE | 6-6 | 21-61-81 | D13460A | | A04 | | D06754P | 4 | | | ALL | |
| 230R | 24 | PL | JE | 0-0 | 21-61-81 | D13460A | | A05 | | D06754P | 3 | | | ALL | |
| 231B | 24 | PW | JF | 3-5 | 22-15-11 | D04853P | | 13 | | TB0119G | 144 | 2 | | ALL | |
| 231R | 24 | PW | JF | 0-0 | 22-15-11 | D04853P | | 12 | | TB0119G | 143 | 2 | | ALL | |
| 231Z | | | JF | 0-0 | 22-15-11 | D04853P | | 14 | | GDY0007 | S.. | 2 | | 050-099, 277-299 | |
| 231Z | | | JF | 0-0 | 22-15-11 | D04853P | | 14 | | GDY0008 | S.. | 2 | | 150-199, 275-276 | |
| 232B | 24 | PL | JG | 6-4 | 21-61-81 | D06754P | | 13 | | D13460B | A13 | | | ALL | |
| 232R | 24 | PL | JG | 0-0 | 21-61-81 | D06754P | | 12 | | D13460B | A15 | | | ALL | |
| 235W | 24 | 7K | JJ | 3-3 | 34-43-21 | D05607P | | 5 | | TB0211G | 7 | 2 | | ALL | |
| 235WB | 24 | 7K | JJ | 0-0 | 34-43-21 | D05607P | | 4 | | TB0211G | 1 | 2 | | ALL | |
| 235Z | | | JJ | 0-0 | 34-43-21 | D05607P | | 6 | | TB0211G | REF | | JJ | ALL | |
| 236B | 24 | PW | JK | 3-0 | 22-12-11 | D05607P | | 2 | | TB0119F | C118 | 2 | | ALL | |
| 236R | 24 | PW | JK | 0-0 | 22-12-11 | D05607P | | 1 | | TB0119F | A118 | 2 | | ALL | |
| 236Z | | | JK | 0-0 | 22-12-11 | D05607P | | 3 | | GDY0002 | S.. | 2 | | ALL | |
| 237B | 24 | PW | JL | 5-0 | 34-43-11 | D04829P | | 5 | | TB0119H | 63 | 2 | | ALL | |
| 237R | 24 | PW | JL | 0-0 | 34-43-11 | D04829P | | 4 | | TB0119H | 61 | 2 | | ALL | |
| 237Z | | | JL | 0-0 | 34-43-11 | D04829P | | 6 | | GDY0010 | S.. | 2 | | ALL | |
| 238W | 24 | 7K | JM | 3-4 | 34-43-11 | D04829P | | 1 | | TB0211G | 7 | 2 | | 050-099, 151 | |
| 238WB | 24 | 7K | JM | 0-0 | 34-43-11 | D04829P | | 2 | | TB0211G | 6 | 2 | | 050-099, 151 | |
| 238Z | | | JM | 0-0 | 34-43-11 | D04829P | | 3 | | TB0211G | REF | | JM | 050-099, 151 | |
| 239B | 24 | PW | JN | 2-10 | 22-41-12 | TB0119F | | C129 | 2 | D04525P | 19 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 46

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0109 | 286T0109 | | | E1-5 SHELF L (continued) | | | | | | | | | | | |
| 239R | 24 | PW | JN | | 0-0 | 22-41-12 | TB0119F | A129 | 2 | | D04525P | 18 | | | ALL |
| 239Z | | | JN | | 0-0 | 22-41-12 | GDY0006 | S.. | 2 | | D04525P | 20 | | | ALL |
| 256B | 22 | PB | KF | | 6-7 | 21-61-81 | D06754P | | 24 | | TB0119Y | C087 | BJ | | 050-099, 151-199, 275-299 |
| 256R | 22 | PB | KF | | 0-0 | 21-61-81 | D06754P | | 23 | | TB0119Y | A087 | BJ | | 050-099, 151-199, 275-299 |
| 257B | 22 | PB | KG | | 6-7 | 21-61-81 | D06754P | | 1 | | TB0119Y | C087 | BJ | | 050-099, 151-199, 275-299 |
| 257R | 22 | PB | KG | | 0-0 | 21-61-81 | D06754P | | 2 | | TB0119Y | A087 | BJ | | 050-099, 151-199, 275-299 |
| 301B | 24 | PM | MA | | 6-0 | 21-61-61 | D06732P | | 4 | | D13460A | B01 | | | ALL |
| 301R | 24 | PM | MA | | 0-0 | 21-61-61 | D06732P | | 5 | | D13460A | B02 | | | ALL |
| 301Y | 24 | PM | MA | | 0-0 | 21-61-61 | D06732P | | 6 | | D13460A | B03 | | | ALL |
| 302B | 24 | PM | MB | | 4-9 | 21-61-61 | D13460A | B10 | | | D06734P | 18 | | | ALL |
| 302R | 24 | PM | MB | | 0-0 | 21-61-61 | D13460A | B11 | | | D06734P | 17 | | | ALL |
| 302Y | 24 | PM | MB | | 0-0 | 21-61-61 | D13460A | B12 | | | D06734P | 16 | | | ALL |
| 303B | 24 | PM | MC | | 4-9 | 21-61-71 | D13460A | C01 | | | D06732P | 15 | | | ALL |
| 303R | 24 | PM | MC | | 0-0 | 21-61-71 | D13460A | C02 | | | D06732P | 16 | | | ALL |
| 303Y | 24 | PM | MC | | 0-0 | 21-61-71 | D13460A | C03 | | | D06732P | 17 | | | ALL |
| 304B | 24 | PM | MD | | 4-9 | 21-61-71 | D13460A | C10 | | | D06734P | 20 | | | ALL |
| 304R | 24 | PM | MD | | 0-0 | 21-61-71 | D13460A | C11 | | | D06734P | 19 | | | ALL |
| 304Y | 24 | PM | MD | | 0-0 | 21-61-71 | D13460A | C12 | | | D06734P | 21 | | | ALL |
| 305B | 24 | PM | ME | | 6-0 | 21-61-81 | D06752P | | 1 | | D13460A | A01 | | | ALL |
| 305R | 24 | PM | ME | | 0-0 | 21-61-81 | D06752P | | 2 | | D13460A | A02 | | | ALL |
| 305Y | 24 | PM | ME | | 0-0 | 21-61-81 | D06752P | | 3 | | D13460A | A03 | | | ALL |
| 306B | 24 | PM | MF | | 6-6 | 21-61-81 | D13460A | A10 | | | D06754P | 6 | | | ALL |
| 306R | 24 | PM | MF | | 0-0 | 21-61-81 | D13460A | A11 | | | D06754P | 5 | | | ALL |
| 306Y | 24 | PM | MF | | 0-0 | 21-61-81 | D13460A | A12 | | | D06754P | 7 | | | ALL |
| 517 | 22 | PA | | | 3-5 | 21-66-11 | D05525P | | 17 | | D06752P | 10 | | | 050-099, 162-199 |
| 518 | 22 | PA | | | 3-4 | 21-66-11 | D05525P | | 18 | | D06752P | 11 | | | 050-099, 162-199 |
| 519 | 22 | PA | | | 3-4 | 21-66-11 | D05525P | | 19 | | D06752P | 12 | | | 050-099, 162-199 |
| 520 | 22 | PA | | | 3-10 | 21-66-41 | D05525P | | 20 | | TB0119G | 70 | 2 | | 050-099, 162-199 |
| 520 | 22 | PA | | | 4-0 | 21-66-41 | D05525P | | 20 | | TB0119G | 70 | 2 | | 150, 152-157 |
| 521 | 22 | PA | | | 3-10 | 21-66-31 | D06752P | | 7 | | TB0119G | 70 | 2 | | 050-099, 162-199 |
| 521 | 22 | PA | | | 4-10 | 21-66-31 | D06752P | | 7 | | TB0119G | 70 | 2 | | 150, 152-157 |
| 522 | 22 | PA | | | 3-4 | 21-66-21 | D05525P | | 21 | | D06752P | 5 | | | 050-099, 162-199 |
| 523 | 22 | PA | | | 4-10 | 21-66-41 | TB0119G | | 70 | 2 | D06752P | 8 | | | 150, 152-157 |
| 523 | 22 | PA | | | 4-8 | 21-66-41 | TB0119G | | 70 | 2 | D06752P | 8 | | | 162-199 |
| 601 | 20 | UA | | | 1-6 | 34-46-11 | D00435B | | | FE | GDX0004 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 47

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|---|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0109 | 286T0109 | | | E1-5 SHELF L (continued) | | | | | | | | | | | | |
| 601B | 24 | PW | YA | | 3-0 | 34-46-11 | D05573P | | 2 | | | D00435B | D01 | | | ALL |
| 601R | 24 | PW | YA | | 0-0 | 34-46-11 | D05573P | | 1 | | | D00435B | C01 | | | ALL |
| 601Z | | | YA | | 0-0 | 34-46-11 | D05573P | | 3 | | | D00435B | | | FE | ALL |
| 602 | 20 | UA | | | 1-6 | 34-46-11 | D00435B | | | | FF | GDX0004 | S.. | 2 | | ALL |
| 602B | 24 | PW | YB | | 2-7 | 34-46-11 | D05609J | | 2 | | | D00435B | B06 | | | ALL |
| 602R | 24 | PW | YB | | 0-0 | 34-46-11 | D05609J | | 1 | | | D00435B | A06 | | | ALL |
| 602Z | | | YB | | 0-0 | 34-46-11 | D05609J | | 3 | | | D00435B | | | FF | ALL |
| 603B | 24 | PW | YC | | 3-2 | 34-46-12 | TB0119G | | 134 | 2 | | D00435B | B11 | | | ALL |
| 603R | 24 | PW | YC | | 0-0 | 34-46-12 | TB0119G | | 133 | 2 | | D00435B | A11 | | | ALL |
| 603Z | | | YC | | 0-0 | 34-46-12 | GDY0006 | | S.. | 2 | | D00435B | DED | | | ALL |
| 604 | 20 | UA | | | 1-6 | 34-46-12 | D00435B | | | | FH | GDX0004 | S.. | 2 | | ALL |
| 604B | 24 | PW | YD | | 3-2 | 34-46-12 | D04853P | | 19 | | | D00435B | D11 | | | ALL |
| 604R | 24 | PW | YD | | 0-0 | 34-46-12 | D04853P | | 18 | | | D00435B | C11 | | | ALL |
| 604Z | | | YD | | 0-0 | 34-46-12 | D04853P | | 20 | | | D00435B | | | FH | ALL |
| 605 | 20 | UA | | | 1-6 | 34-46-11 | D00435B | | | | FI | GDX0004 | S.. | 2 | | ALL |
| 605B | 24 | PW | YE | | 3-0 | 34-46-11 | D04525P | | 2 | | | D00435B | B13 | | | ALL |
| 605R | 24 | PW | YE | | 0-0 | 34-46-11 | D04525P | | 1 | | | D00435B | A13 | | | ALL |
| 605Z | | | YE | | 0-0 | 34-46-11 | D04525P | | 3 | | | D00435B | | | FI | ALL |
| 606 | 20 | UA | | | 1-6 | 34-46-11 | D00435B | | | | FJ | GDX0004 | S.. | 2 | | ALL |
| 606B | 24 | PW | YF | | 3-0 | 34-46-11 | D05525P | | 8 | | | D00435B | D13 | | | ALL |
| 606R | 24 | PW | YF | | 0-0 | 34-46-11 | D05525P | | 7 | | | D00435B | C13 | | | ALL |
| 606Z | | | YF | | 0-0 | 34-46-11 | D05525P | | 9 | | | D00435B | | | FJ | ALL |
| 607 | 20 | UA | | | 1-6 | 34-46-11 | D00435B | | | | YG | GDX0004 | S.. | 2 | | ALL |
| 607B | 24 | PW | YG | | 3-0 | 34-46-11 | D04525P | | 22 | | | D00435B | D10 | | | ALL |
| 607R | 24 | PW | YG | | 0-0 | 34-46-11 | D04525P | | 21 | | | D00435B | C10 | | | ALL |
| 607Z | | | YG | | 0-0 | 34-46-11 | D04525P | | 23 | | | D00435B | | | YG | ALL |
| 608 | 24 | PK | | | 3-0 | 34-46-12 | TB0119G | | 103 | 2 | | D00435A | D12 | | | 050-099, 151 |
| 609 | 24 | PK | | | 3-0 | 34-46-12 | TB0119G | | 103 | 2 | | D00435B | C07 | | | ALL |
| 611 | 22 | PA | | | 3-4 | 34-22-36 | D05817P | | 4 | | | D05607P | 14 | | | ALL |
| 612 | 22 | PA | | | 5-1 | 34-45-12 | D04853P | | 54 | | | TB0119D | A094 | 2 | | 050-099, 150-152, 155-199, 275-299 |
| 612 | 22 | PA | | | 5-1 | 34-45-12 | D04853P | | 54 | | | TB0119D | A113 | 2 | | 153-154 |
| 613 | 22 | PA | | | 3-0 | 34-45-12 | TB0119D | | A094 | 2 | | TB0119D | A095 | 2 | | 050-099, 150-152, 155-156, 162-166, 275-276 |
| 614 | 22 | PA | | | 3-2 | 34-45-12 | TB0119D | | A095 | 2 | | TB0119D | A097 | 2 | | 050-099, 150-152, 155-156, 162-166 |
| 614 | 22 | PA | | | 3-2 | 34-45-12 | TB0119D | | A095 | 2 | | TB0119D | A090 | 2 | | 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 48

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|---------------------------------|-------|------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0109 | 286T0109 | E1-5 SHELF L (continued) | | | | | | | | | | | | | | |
| 615 | 22 | PA | | 5-4 | 34-46-11 | D05257P | | 2 | | | TB0119D | C095 | 2 | | 050-099, 150-152, 155-199, 275-299 | |
| 615 | 22 | PA | | 3-0 | 34-46-11 | D05257P | | 2 | | | TB0119D | C095 | 2 | | 153-154 | |
| 616 | 22 | PA | | 4-8 | 34-46-11 | TB0119D | | C097 | 2 | | TB0119H | 139 | 2 | | 050-099, 150-152, 155-199, 277-299 | |
| 616 | 22 | PA | | 4-1 | 34-46-11 | TB0119D | | C097 | 2 | | TB0119H | 139 | 2 | | 153-154 | |
| 616 | 22 | PA | | 3-0 | 34-46-11 | TB0119D | | C097 | 2 | | TB0119H | 139 | 2 | | 275-276 | |
| 617 | 22 | PA | | 6-0 | 34-46-11 | TB0119D | | C094 | 2 | | TB0119G | 116 | 2 | | ALL | |
| 618 | 24 | PK | | 4-0 | 21-26-31 | D13560A | | C03 | | | TB0119G | 59 | 2 | | ALL | |
| 619 | 24 | PK | | 3-10 | 21-26-31 | D06734P | | 38 | | | TB0119G | 59 | 2 | | ALL | |
| 620 | 22 | PA | | 3-10 | 21-26-31 | D06734P | | 46 | | | TB0119G | 60 | 2 | | ALL | |
| 621 | 22 | PQ | YU | 4-0 | 21-51-11 | TB0119G | | 60 | 2 | | TB0119Y | A189 | BJ | | ALL | |
| 621Z | | | YU | 0-0 | 21-51-11 | TB0119G | | DED | | | TB0119Y | DED | | | ALL | |
| 622 | 22 | PA | | 5-1 | 34-45-12 | D04853P | | 34 | | | TB0119D | A114 | 2 | | 153-154 | |
| 622 | 22 | PA | | 5-1 | 34-45-12 | D04853P | | 34 | | | TB0119D | A095 | 2 | | 157, 167-199, 277-299 | |
| 623 | 22 | PA | | 5-1 | 34-45-12 | D04853P | | 35 | | | TB0119D | A115 | 2 | | 153-154 | |
| 623 | 22 | PA | | 5-1 | 34-45-12 | D04853P | | 35 | | | TB0119D | A097 | 2 | | 157, 167-199, 277-299 | |
| 701 | 22 | PA | | 5-3 | 34-46-11 | D05257P | | 1 | | | TB0119D | C094 | 2 | | 050-099, 150-152, 155-199, 275-299 | |
| 701 | 22 | PA | | 3-0 | 34-46-11 | D05257P | | 1 | | | TB0119D | C094 | 2 | | 153-154 | |
| 702 | 20 | PA | | 3-0 | 34-46-11 | D04203P | | 1 | | | D00435C | 2 | | | ALL | |
| 703 | 22 | PA | | 5-0 | 34-46-11 | TB0119D | | C095 | 2 | | D00435B | D03 | | | 050-099 | |
| 703 | 22 | PA | | 4-0 | 34-46-11 | TB0119D | | C095 | 2 | | D00435B | D03 | | | 151 | |
| 704 | 24 | PK | | 2-7 | 34-46-11 | D05257P | | 3 | | | D00435B | D09 | | | ALL | |
| 705 | 24 | PK | | 3-3 | 34-46-12 | TB0119D | | A015 | 2 | | TB0119G | 17 | 2 | | ALL | |
| 706 | 24 | PK | | 3-4 | 34-46-12 | D00435B | | B09 | | | TB0119G | 17 | 2 | | ALL | |
| 707 | 24 | PK | | 3-3 | 34-46-12 | D05523P | | 13 | | | TB0119G | 17 | 2 | | ALL | |
| 708 | 24 | PK | | 4-3 | 34-46-12 | TB0119G | | 180 | 2 | | D00435B | A09 | | | ALL | |
| 709 | 22 | PA | | 3-9 | 34-46-12 | TB0119G | | 103 | 2 | | D04853P | 25 | | | ALL | |
| 712 | 24 | PK | | 3-6 | 34-46-12 | D05523P | | 15 | | | TB0119G | 19 | 2 | | ALL | |
| 713 | 20 | PA | | 2-2 | 34-46-11 | D00435C | | 3 | | | GDX0004 | A.. | 2 | | ALL | |
| 714 | 20 | PA | | 2-2 | 34-46-11 | D00435C | | 4 | | | GDX0004 | D.. | 2 | | ALL | |
| 715 | 24 | PK | | 3-3 | 34-46-12 | D04525P | | 6 | | | TB0119D | C018 | 2 | | 050-099, 150-199, 275-278 | |
| 716 | 24 | PK | | 3-3 | 34-46-12 | D00435B | | C09 | | | TB0119G | 19 | 2 | | ALL | |
| 717 | 24 | PK | | 3-8 | 34-46-12 | D04853P | | 7 | | | TB0119G | 19 | 2 | | ALL | |
| 718 | 24 | PK | | 3-6 | 31-51-21 | D05525P | | 6 | | | TB0119G | 116 | 2 | | ALL | |
| 719 | 22 | PA | | 3-0 | 34-46-11 | D00435B | | B07 | | | TB0119G | 116 | 2 | | 050-099, 151 | |
| 720 | 22 | PA | | 3-0 | 34-46-11 | D00435B | | D14 | | | TB0119H | 119 | 2 | | 050-099, 151 | |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 49

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|---------|-------------|------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type | Splice |
| W0109 | 286T0109 | | | E1-5 SHELF L (continued) | | | | | | | | | | | | |
| 728 | 22 | | PA | | 3-0 | 34-46-11 | D00435A | | C12 | | | TB0119G | 110 | 2 | | 050-099, 151 |
| 730 | 24 | | PK | | 3-7 | 34-46-12 | TB0119D | | C015 | 2 | | D04525P | 4 | | | ALL |
| 731 | 24 | | PK | | 3-0 | 34-46-12 | D00435B | | CAP | Y | | TB0119D | A018 | 2 | | 050-099, 151 |
| 732 | 24 | | PK | | 3-4 | 34-46-12 | TB0119D | | A018 | 2 | | TB0119D | A014 | 2 | | 050-099, 150-199, 275-278 |
| 733 | 24 | | PK | | 3-2 | 34-46-12 | TB0119D | | A014 | 2 | | TB0119D | A016 | 2 | | 050-099, 150-199, 275-278 |
| 741 | 22 | | PA | | 2-10 | 34-46-11 | D00435B | | C08 | | | TB0119H | 119 | 2 | | 050-099, 151 |
| 900 | 22 | | PA | | 4-0 | 34-46-11 | D00435A | | D11 | | | SMZ0001 | | S | | 050-099, 151 |
| 9001 | 20 | | PA | | 1-0 | 34-46-13 | GDX0004 | | S.. | 2 | | D00435A | | | FG | 150, 152-199, 275-299 |
| 9002 | 20 | | PA | | 1-0 | 34-46-13 | D09127 | | | | FL | GDY0012 | S.. | 2 | | 150, 152-199, 275-299 |
| 9003 | 20 | | PA | | 1-0 | 34-46-13 | D09128 | | | | FK | GDY0012 | S.. | 2 | | 150, 152-199, 275-299 |
| 9004 | 20 | | PA | | 1-0 | 34-46-13 | GDY0012 | | S.. | 2 | | D09127 | | | FB | 150, 152-199, 275-299 |
| 9005 | 20 | | PA | | 1-0 | 34-46-13 | GDY0012 | | S.. | 2 | | D09127 | | | FA | 150, 152-199, 275-299 |
| 9006 | 20 | | PA | | 1-0 | 34-46-13 | GDY0012 | | S.. | 2 | | D09128 | | | FD | 150, 152-199, 275-299 |
| 9007 | 20 | | PA | | 1-0 | 34-46-13 | GDY0012 | | S.. | 2 | | D09128 | | | FM | 150, 152-199, 275-299 |
| 9008 | 20 | | PA | | 1-0 | 34-46-13 | GDX0004 | | S.. | 2 | | D00435A | | | FZ | 150, 152-199, 275-299 |
| 9009 | 20 | | PA | | 1-0 | 34-46-13 | D09129 | | | | FX | GDY0012 | S.. | 2 | | 150, 152-199, 275-299 |
| 901 | 22 | | PA | | 4-0 | 34-46-11 | D00435B | | C02 | | | SMZ0001 | | S | | 050-099, 151 |
| 9010 | 20 | | PA | | 1-0 | 34-46-13 | D09130 | | | | FW | GDY0012 | S.. | 2 | | 150, 152-199, 275-299 |
| 9011 | 20 | | PA | | 1-0 | 34-46-13 | GDY0012 | | S.. | 2 | | D09129 | | | FP | 150, 152-199, 275-299 |
| 9012 | 20 | | PA | | 1-0 | 34-46-13 | GDY0012 | | S.. | 2 | | D09129 | | | FN | 150, 152-199, 275-299 |
| 9013 | 20 | | PA | | 1-0 | 34-46-13 | GDY0012 | | S.. | 2 | | D09130 | | | FT | 150, 152-199, 275-299 |
| 9014 | 20 | | PA | | 1-0 | 34-46-13 | GDY0012 | | S.. | 2 | | D09130 | | | FR | 150, 152-199, 275-299 |
| 9015 | 20 | | PA | | 1-0 | 34-46-13 | GDX0004 | | S.. | 2 | | D00435A | | | FY | 150, 152-199, 275-299 |
| 9015B | 24 | | PW | P | 0-0 | 34-46-13 | TB0119H | | 63 | 2 | | D00435A | D05 | | | 150, 152-199, 275-299 |
| 9015R | 24 | | PW | P | 5-0 | 34-46-13 | TB0119H | | 61 | 2 | | D00435A | C05 | | | 150, 152-199, 275-299 |
| 9016 | 20 | | PA | | 1-0 | 34-46-13 | GDX0004 | | S.. | 2 | | D00435A | | | FS | 150, 152-199, 275-299 |
| 9016B | 24 | | PW | Q | 0-0 | 34-46-13 | TB0119Y | | C009 | BJ | | D00435A | B08 | | | 150, 152-199, 275-299 |
| 9016R | 24 | | PW | Q | 5-0 | 34-46-13 | TB0119Y | | A009 | BJ | | D00435A | A08 | | | 150, 152-199, 275-299 |
| 9017B | 24 | | PW | W | 5-0 | 34-22-29 | TB0119Y | | C009 | BJ | | TB0119F | C007 | 2 | | 150, 152-199, 275-299 |
| 9017R | 24 | | PW | W | 0-0 | 34-22-29 | TB0119Y | | A009 | BJ | | TB0119F | A007 | 2 | | 150, 152-199, 275-299 |
| 9018 | 20 | | PA | | 1-0 | 34-46-13 | GDX0004 | | S.. | 2 | | D00435B | | | FQ | 150, 152-199, 275-299 |
| 9018B | 24 | | PW | K | 0-0 | 34-46-13 | D05607P | | 19 | | | D00435B | B12 | | | 150, 152-199, 275-299 |
| 9018R | 24 | | PW | K | 5-0 | 34-46-13 | D05607P | | 18 | | | D00435B | A12 | | | 150, 152-199, 275-299 |
| 901W | 24 | | PW | H | 5-0 | 34-46-13 | TB0119Y | | A191 | BJ | | D00435A | A03 | | | 150, 152-199, 275-299 |
| 901WB | 24 | | PW | H | 0-0 | 34-46-13 | TB0119Y | | A192 | BJ | | D00435A | B03 | | | 150, 152-199, 275-299 |
| 901Z | | | | H | 0-0 | 34-46-13 | TB0119Y | | DED | | | D00435A | | | FG | 150, 152-199, 275-299 |
| 902 | 22 | | PA | | 4-0 | 34-46-11 | D00435B | | A04 | | | SMZ0002 | | S | | 050-099, 151 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 50

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0109 | 286T0109 | | | E1-5 SHELF L (continued) | | | | | | | | | | | |
| 902W | 24 | PW | G | | 2-0 | 34-46-13 | D09127 | 8 | | | TB0119Y | A191 | BJ | | 150, 152-199, 275-299 |
| 902WB | 24 | PW | G | | 0-0 | 34-46-13 | D09127 | 4 | | | TB0119Y | A192 | BJ | | 150, 152-199, 275-299 |
| 902Z | | | G | | 0-0 | 34-46-13 | D09127 | | | FL | TB0119Y | DED | | | 150, 152-199, 275-299 |
| 903 | 22 | PA | | | 4-0 | 34-46-11 | D00435B | C14 | | | SMZ0002 | | S | | 050-099, 151 |
| 903W | 24 | PW | F | | 2-0 | 34-46-13 | D09128 | 4 | | | TB0119Y | A191 | BJ | | 150, 152-199, 275-299 |
| 903WB | 24 | PW | F | | 0-0 | 34-46-13 | D09128 | 2 | | | TB0119Y | A192 | BJ | | 150, 152-199, 275-299 |
| 903Z | | | F | | 0-0 | 34-46-13 | D09128 | | | FK | TB0119Y | DED | | | 150, 152-199, 275-299 |
| 904 | 22 | PA | | | 4-0 | 34-46-11 | SMZ0001 | | S | | TB0119H | 119 | 2 | | 050-099, 151 |
| 904W | 24 | PW | C | | 7-0 | 34-46-13 | D09123P | 5 | | | D09127 | 7 | | | 150, 152-199, 275-299 |
| 904WB | 24 | PW | C | | 0-0 | 34-46-13 | D09123P | 6 | | | D09127 | 5 | | | 150, 152-199, 275-299 |
| 904Z | | | C | | 0-0 | 34-46-13 | D09123P | 7 | | | D09127 | | | FB | 150, 152-199, 275-299 |
| 905 | 22 | PA | | | 4-0 | 34-46-11 | SMZ0002 | | S | | TB0119H | 119 | 2 | | 050-099, 151 |
| 905W | 24 | PW | B | | 5-0 | 34-46-13 | D09123P | 8 | | | D09127 | 14 | | | 150, 152-199, 275-299 |
| 905WB | 24 | PW | B | | 0-0 | 34-46-13 | D09123P | 9 | | | D09127 | 3 | | | 150, 152-199, 275-299 |
| 905Z | | | B | | 0-0 | 34-46-13 | D09123P | 10 | | | D09127 | | | FA | 150, 152-199, 275-299 |
| 906 | 20 | UA | | | 1-6 | 34-46-11 | D00435B | | | FC | GD00004 | S.. | 2 | | 050-099, 150-166, 275-299 |
| 906B | 24 | PW | FH | | 0-0 | 34-46-11 | D04525P | 13 | | | D00435B | B10 | | | 050-099, 150-166, 275-299 |
| 906R | 24 | PW | FH | | 3-0 | 34-46-11 | D04525P | 12 | | | D00435B | A10 | | | 050-099, 150-166, 275-299 |
| 906Z | | | FH | | 0-0 | 34-46-11 | D04525P | 14 | | | D00435B | | | FC | 050-099, 150-166, 275-299 |
| 907 | 22 | PA | | | 10-0 | 34-46-13 | TB0119X | A161 | BJ | | D00435A | C02 | | | 150, 152-199, 275-299 |
| 907W | 24 | PW | D | | 7-0 | 34-46-13 | D09123P | 16 | | | D09128 | 3 | | | 150, 152-199, 275-299 |
| 907WB | 24 | PW | D | | 0-0 | 34-46-13 | D09123P | 17 | | | D09128 | 13 | | | 150, 152-199, 275-299 |
| 907Z | | | D | | 0-0 | 34-46-13 | D09123P | 18 | | | D09128 | | | FM | 150, 152-199, 275-299 |
| 908 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | B161 | BJ | | D00435A | B05 | | | 150, 152-199, 275-299 |
| 908W | 24 | PW | T | | 5-0 | 34-46-13 | TB0119Y | A091 | BJ | | D00435A | C03 | | | 150, 152-199, 275-299 |
| 908WB | 24 | PW | T | | 0-0 | 34-46-13 | TB0119Y | A092 | BJ | | D00435A | D03 | | | 150, 152-199, 275-299 |
| 908Z | | | T | | 0-0 | 34-46-13 | TB0119Y | DED | | | D00435A | | | FZ | 150, 152-199, 275-299 |
| 909 | 22 | PA | | | 5-0 | 34-46-13 | TB0119Y | A171 | BJ | | D00435A | A12 | | | 150, 152-199, 275-299 |
| 909W | 24 | PW | R | | 2-0 | 34-46-13 | D09129 | 8 | | | TB0119Y | A091 | BJ | | 150, 152-199, 275-299 |
| 909WB | 24 | PW | R | | 0-0 | 34-46-13 | D09129 | 4 | | | TB0119Y | A092 | BJ | | 150, 152-199, 275-299 |
| 909Z | | | R | | 0-0 | 34-46-13 | D09129 | | | FX | TB0119Y | DED | | | 150, 152-199, 275-299 |
| 910 | 22 | PA | | | 2-0 | 34-46-13 | TB0119D | C175 | 2 | | TB0119Y | A171 | BJ | | 150, 152-199, 275-299 |
| 910W | 24 | PW | N | | 2-0 | 34-46-13 | D09130 | 4 | | | TB0119Y | A091 | BJ | | 150, 152-199, 275-299 |
| 910WB | 24 | PW | N | | 0-0 | 34-46-13 | D09130 | 2 | | | TB0119Y | A092 | BJ | | 150, 152-199, 275-299 |
| 910Z | | | N | | 0-0 | 34-46-13 | D09130 | | | FW | TB0119Y | DED | | | 150, 152-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0100
Page 51
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|-----------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0109 | 286T0109 | | | E1-5 SHELF L (continued) | | | | | | | | | | | | | |
| 911 | 22 | | PA | | 5-0 | 34-46-13 | TB0119H | 139 | 2 | | | | TB0119D | A175 | 2 | | 150, 152-199, 275-299 |
| 911W | 24 | | PW | U | 7-0 | 34-46-13 | TB0211G | 7 | 2 | | | | D09129 | 7 | | | 150, 152-199, 275-299 |
| 911WB | 24 | | PW | U | 0-0 | 34-46-13 | TB0211G | 6 | 2 | | | | D09129 | 5 | | | 150, 152-199, 275-299 |
| 911Z | | | | U | 0-0 | 34-46-13 | TB0211G | DED | | | | | D09129 | | | FP | 150, 152-199, 275-299 |
| 912 | 22 | | PA | | 5-0 | 34-46-13 | TB0119X | C161 | BJ | | | | D00435A | A10 | | | 150, 152-199, 275-299 |
| 912W | 24 | | PW | J | 7-0 | 34-46-13 | D04829P | 1 | | | | | D09129 | 14 | | | 150, 152-199, 275-299 |
| 912WB | 24 | | PW | J | 0-0 | 34-46-13 | D04829P | 2 | | | | | D09129 | 3 | | | 150, 152-199, 275-299 |
| 912Z | | | | J | 0-0 | 34-46-13 | D04829P | 3 | | | | | D09129 | | | FN | 150, 152-199, 275-299 |
| 913 | 22 | | PA | | 2-0 | 34-46-13 | TB0119Y | A171 | BJ | | | | TB0119X | C161 | BJ | | 150, 152-199, 275-299 |
| 913W | 24 | | PW | M | 7-0 | 34-46-13 | TB0211G | 9 | 2 | | | | D09130 | 5 | | | 150, 152-199, 275-299 |
| 913WB | 24 | | PW | M | 0-0 | 34-46-13 | TB0211G | 8 | 2 | | | | D09130 | 1 | | | 150, 152-199, 275-299 |
| 913Z | | | | M | 0-0 | 34-46-13 | TB0211G | DED | | | | | D09130 | | | FT | 150, 152-199, 275-299 |
| 914 | 22 | | PA | | 5-0 | 34-46-13 | TB0119Y | C171 | BJ | | | | D00435A | D04 | | | 150, 152-199, 275-299 |
| 914W | 24 | | PW | L | 7-0 | 34-46-13 | D04849P | 5 | | | | | D09130 | 3 | | | 150, 152-199, 275-299 |
| 914WB | 24 | | PW | L | 0-0 | 34-46-13 | D04849P | 6 | | | | | D09130 | 13 | | | 150, 152-199, 275-299 |
| 914Z | | | | L | 0-0 | 34-46-13 | D04849P | 7 | | | | | D09130 | | | FR | 150, 152-199, 275-299 |
| 915 | 22 | | PA | | 2-0 | 34-46-13 | TB0119D | C178 | 2 | | | | TB0119Y | C171 | BJ | | 150, 152-199, 275-299 |
| 915Z | | | | P | 0-0 | 34-46-13 | TB0119H | DED | | | | | D00435A | | | FY | 150, 152-199, 275-299 |
| 916 | 22 | | PA | | 4-0 | 34-46-13 | TB0119D | A178 | 2 | | | | D09127 | 1 | | | 150, 152-199, 275-299 |
| 916Z | | | | Q | 0-0 | 34-46-13 | TB0119Y | DED | | | | | D00435A | | | FS | 150, 152-199, 275-299 |
| 917 | 22 | | PA | | 7-0 | 34-46-13 | D09123P | 3 | | | | | D09127 | 13 | | | 150, 152-199, 275-299 |
| 917Z | | | | W | 0-0 | 34-22-29 | TB0119Y | DED | | | | | GDY0001 | S.. | 2 | | 150, 152-199, 275-299 |
| 918 | 22 | | PA | | 7-0 | 34-46-13 | D09127 | 2 | | | | | D09123P | 4 | | | 150, 152-199, 275-299 |
| 918Z | | | | K | 0-0 | 34-46-13 | D05607P | 20 | | | | | D00435B | | | FQ | 150, 152-199, 275-299 |
| 919 | 22 | | PA | | 5-0 | 34-46-13 | TB0119Y | A172 | BJ | | | | D00435A | C12 | | | 150, 152-199, 275-299 |
| 920 | 22 | | PA | | 2-0 | 34-46-13 | TB0119D | C179 | 2 | | | | TB0119Y | A172 | BJ | | 150, 152-199, 275-299 |
| 921 | 22 | | PA | | 5-0 | 34-46-13 | TB0119G | 110 | 2 | | | | TB0119D | A179 | 2 | | 150, 152-199, 275-299 |
| 922 | 22 | | PA | | 5-0 | 34-46-13 | TB0119Y | C172 | BJ | | | | D00435A | A11 | | | 150, 152-199, 275-299 |
| 923 | 22 | | PA | | 2-0 | 34-46-13 | TB0119D | C169 | 2 | | | | TB0119Y | C172 | BJ | | 150, 152-199, 275-299 |
| 924 | 22 | | PA | | 4-0 | 34-46-13 | D09129 | 1 | | | | | TB0119D | A169 | 2 | | 150, 152-199, 275-299 |
| 925 | 22 | | PA | | 7-0 | 34-46-13 | D09123P | 24 | | | | | D09129 | 13 | | | 150, 152-199, 275-299 |
| 926 | 22 | | PA | | 7-0 | 34-46-13 | D09123P | 25 | | | | | D09129 | 2 | | | 150, 152-199, 275-299 |
| 927 | 22 | | PA | | 5-0 | 34-46-13 | TB0119Y | A173 | BJ | | | | D00435A | B12 | | | 150, 152-199, 275-299 |
| 928 | 22 | | PA | | 5-0 | 34-46-13 | TB0119X | D161 | BJ | | | | D00435B | D14 | | | 150, 152-199, 275-299 |
| 929 | 22 | | PA | | 2-0 | 34-46-13 | TB0119Y | A173 | BJ | | | | TB0119X | D161 | BJ | | 150, 152-199, 275-299 |
| 930 | 22 | | PA | | 5-0 | 34-46-13 | TB0119X | A162 | BJ | | | | D00435B | D04 | | | 150, 152-199, 275-299 |
| 931 | 22 | | PA | | 2-0 | 34-46-13 | TB0119Z | 167 | BJ | | | | TB0119X | A162 | BJ | | 150, 152-199, 275-299 |
| 932 | 22 | | PA | | 5-0 | 34-46-13 | TB0119X | B162 | BJ | | | | D00435B | A08 | | | 150, 152-199, 275-299 |
| 933 | 22 | | PA | | 2-0 | 34-46-13 | TB0119Z | 167 | BJ | | | | TB0119X | B162 | BJ | | 150, 152-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 52

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|-------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0109 | 286T0109 | | | E1-5 SHELF L (continued) | | | | | | | | | | | |
| 934 | 22 | PA | | | 5-0 | 34-46-13 | TB0119Z | 167 | BJ | | D00435B | A03 | | | 150, 152-199, 275-299 |
| 935 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | C162 | BJ | | D00435B | A02 | | | 150, 152-199, 275-299 |
| 936 | 22 | PA | | | 2-0 | 34-46-13 | TB0119Z | 167 | BJ | | TB0119X | C162 | BJ | | 150, 152-199, 275-299 |
| 937 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | D162 | BJ | | D00435B | C08 | | | 150, 152-199, 275-299 |
| 938 | 22 | PA | | | 2-0 | 34-46-13 | TB0119Z | 167 | BJ | | TB0119X | D162 | BJ | | 150, 152-199, 275-299 |
| 939 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | A163 | BJ | | D00435A | D06 | | | 150, 152-199, 275-299 |
| 940 | 22 | PA | | | 2-0 | 34-46-13 | TB0119X | B164 | BJ | | TB0119Y | A174 | BJ | | 150, 152-199, 275-299 |
| 941 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | B163 | BJ | | D00435A | B10 | | | 150, 152-199, 275-299 |
| 942 | 22 | PA | | | 2-0 | 34-46-13 | TB0119X | B163 | BJ | | TB0119Y | C173 | BJ | | 150, 152-199, 275-299 |
| 943 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | C163 | BJ | | D00435A | C10 | | | 150, 152-199, 275-299 |
| 944 | 22 | PA | | | 2-0 | 34-46-13 | TB0119X | C163 | BJ | | TB0119Y | C173 | BJ | | 150, 152-199, 275-299 |
| 945 | 22 | PA | | | 5-0 | 34-46-13 | TB0119Y | C173 | BJ | | D00435B | D03 | | | 150, 152-199, 275-299 |
| 946 | 22 | PA | | | 2-0 | 34-46-13 | TB0119D | C181 | 2 | | TB0119Y | C173 | BJ | | 150, 152-199, 275-299 |
| 947 | 22 | PA | | | 5-0 | 34-46-13 | TB0119D | C095 | 2 | | TB0119D | A181 | 2 | | 150, 152, 155-199, 275-299 |
| 947 | 22 | PA | | | 5-0 | 34-46-13 | TB0119D | C114 | 2 | | TB0119D | A181 | 2 | | 153-154 |
| 948 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | D163 | BJ | | D00435B | B05 | | | 150, 152-199, 275-299 |
| 949 | 22 | PA | | | 2-0 | 34-46-13 | TB0119X | D163 | BJ | | TB0119Y | A174 | BJ | | 150, 152-199, 275-299 |
| 950 | 22 | PA | | | 5-0 | 34-46-13 | TB0119Y | A174 | BJ | | D00435B | D15 | | | 150, 152-199, 275-299 |
| 951 | 22 | PA | | | 5-0 | 34-46-13 | TB0119Y | C174 | BJ | | D00435B | B07 | | | 150, 152-199, 275-299 |
| 952 | 22 | PA | | | 2-0 | 34-46-13 | TB0119D | C182 | 2 | | TB0119Y | C174 | BJ | | 150, 152-199, 275-299 |
| 953 | 22 | PA | | | 5-0 | 34-46-13 | TB0119G | 116 | 2 | | TB0119D | A182 | 2 | | 150, 152-199, 275-299 |
| 954 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | A164 | BJ | | D00435B | B04 | | | 150, 152-199, 275-299 |
| 955 | 22 | PA | | | 2-0 | 34-46-13 | TB0119Y | C174 | BJ | | TB0119X | A164 | BJ | | 150, 152-199, 275-299 |
| 956 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | B164 | BJ | | D00435B | C02 | | | 150, 152-199, 275-299 |
| 957 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | C164 | BJ | | D00435B | A04 | | | 150, 152-199, 275-299 |
| 958 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | D164 | BJ | | D00435B | C04 | | | 150, 152-199, 275-299 |
| 959 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | A165 | BJ | | D00435B | A05 | | | 150, 152-199, 275-299 |
| 960 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | B165 | BJ | | D00435B | B08 | | | 150, 152-199, 275-299 |
| 961 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | C165 | BJ | | D00435B | A15 | | | 150, 152-199, 275-299 |
| 962 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | D165 | BJ | | D00435B | B15 | | | 150, 152-199, 275-299 |
| 963 | 22 | PA | | | 5-0 | 34-46-13 | TB0119X | A166 | BJ | | D00435B | C15 | | | 150, 152-199, 275-299 |
| 964 | 22 | PA | | | 5-0 | 34-46-13 | D09123P | 1 | | | D00435B | A14 | | | 150, 152-199, 275-299 |
| 965 | 22 | PA | | | 5-0 | 34-46-13 | D09123P | 2 | | | D00435A | A01 | | | 150, 152-199, 275-299 |
| 966 | 22 | PA | | | 5-0 | 34-46-13 | TB0119Y | C191 | BJ | | D00435A | D10 | | | 150, 152-199, 275-299 |
| 967 | 22 | PA | | | 2-0 | 34-46-13 | D09127 | 12 | | | TB0119Y | C191 | BJ | | 150, 152-199, 275-299 |
| 968 | 22 | PA | | | 2-0 | 34-46-13 | D09128 | 12 | | | TB0119Y | C191 | BJ | | 150, 152-199, 275-299 |
| 969 | 22 | PA | | | 2-0 | 34-46-13 | TB0119Z | 193 | BJ | | D09127 | 6 | | | 150, 152-199, 275-299 |
| 970 | 22 | PA | | | 2-0 | 34-46-13 | TB0119Z | 193 | BJ | | D09128 | 6 | | | 150, 152-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 53

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|--------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0109 | 286T0109 | | | E1-5 SHELF L (continued) | | | | | | | | | | | | | |
| 971 | 22 | | PA | | 7-0 34-46-13 | D04203P | | 2 | | | | | TB0119Z | 193 | BJ | | 150, 152-199, 275-299 |
| 972 | 22 | | PA | | 2-0 34-46-13 | TB0119Z | | 193 | BJ | | | | D09129 | 6 | | | 150, 152-199, 275-299 |
| 973 | 22 | | PA | | 2-0 34-46-13 | TB0119Z | | 193 | BJ | | | | D09130 | 6 | | | 150, 152-199, 275-299 |
| 974 | 22 | | PA | | 7-0 34-46-13 | D09123P | | 11 | | | | | D09127 | 9 | | | 150, 152-199, 275-299 |
| 975 | 22 | | PA | | 2-0 34-46-13 | TB0119Y | | C192 | BJ | | | | D09127 | 11 | | | 150, 152-199, 275-299 |
| 976 | 22 | | PA | | 7-0 34-46-13 | D09123P | | 12 | | | | | TB0119Y | C192 | BJ | | 150, 152-199, 275-299 |
| 977 | 22 | | PA | | 2-0 34-46-13 | TB0119Y | | C192 | BJ | | | | D09129 | 11 | | | 150, 152-199, 275-299 |
| 978 | 22 | | PA | | 7-0 34-46-13 | D09123P | | 26 | | | | | D09129 | 9 | | | 150, 152-199, 275-299 |
| 979 | 22 | | PA | | 5-0 34-46-13 | D09123P | | 19 | | | | | D00435B | A07 | | | 150, 152-199, 275-299 |
| 980 | 22 | | PA | | 5-0 34-46-13 | D09123P | | 20 | | | | | D00435B | D02 | | | 150, 152-199, 275-299 |
| 981 | 22 | | PA | | 5-0 34-46-13 | D09123P | | 21 | | | | | D00435B | B14 | | | 150, 152-199, 275-299 |
| 982 | 22 | | PA | | 5-0 34-46-13 | D09123P | | 22 | | | | | D00435A | B01 | | | 150, 152-199, 275-299 |
| 983 | 22 | | PA | | 5-0 34-46-13 | D09123P | | 23 | | | | | D00435A | D12 | | | 150, 152-199, 275-299 |
| 984 | 22 | | PA | | 5-0 34-46-13 | TB0119Y | | C091 | BJ | | | | D00435B | C14 | | | 150, 152-199, 275-299 |
| 985 | 22 | | PA | | 2-0 34-46-13 | D09129 | | 12 | | | | | TB0119Y | C091 | BJ | | 150, 152-199, 275-299 |
| 986 | 22 | | PA | | 2-0 34-46-13 | D09130 | | 12 | | | | | TB0119Y | C091 | BJ | | 150, 152-199, 275-299 |
| 987 | 22 | | PA | | 5-0 34-46-12 | D09123P | | 27 | | | | | D00435A | B11 | | | 150, 152-199, 275-299 |
| 988 | 22 | | PA | | 1-0 34-46-13 | TB0119Z | | 167 | BJ | | | | TB0119X | A161 | BJ | | 150, 152-199, 275-299 |
| 989 | 22 | | PA | | 1-0 34-46-13 | TB0119Z | | 167 | BJ | | | | TB0119X | A163 | BJ | | 150, 152-199, 275-299 |
| 990W | 24 | | PW | E | 7-0 34-46-13 | D09123P | | 13 | | | | | D09128 | 5 | | | 150, 152-199, 275-299 |
| 990WB | 24 | | PW | E | 0-0 34-46-13 | D09123P | | 14 | | | | | D09128 | 1 | | | 150, 152-199, 275-299 |
| 990Z | | | | E | 0-0 34-46-13 | D09123P | | 15 | | | | | D09128 | | | FD | 150, 152-199, 275-299 |
| FRA | | | | | 0-4 34-43-21 | TB0211G | | REF | | JJ | | | GDZ0001 | S.. | 2 | | ALL |
| FRB | | | | | 0-4 34-43-11 | TB0211G | | REF | | JM | | | GDZ0001 | S.. | 2 | | 050-099, 151 |

WIRE LIST

D280T132

91-21-11

Section W0100

Page 54 End

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|------------------------------|-------|------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0110 | 286T0110 | AFT MID CABIN MOD (I) | | | | | | | | | | | | | | |
| 005 | 18 | PA | | 6-0 | 33-22-31 | L00192 | =G | C | * | D06028P | 3 | DL | | 050-099 | | |
| 005 | 18 | PA | | 6-0 | 33-22-31 | L00192 | =G | C | * | L00193 | =G | C | | 275-299 | | |
| 006 | 18 | PA | | 6-0 | 33-22-31 | L00192 | =P | C | | D06028P | 2 | DL | | 050-099 | | |
| 006 | 18 | PA | | 7-0 | 33-22-31 | D06028P | 2 | DL | | L00192 | =P | C | | 275-299 | | |
| 007 | 18 | PA | | 6-0 | 33-22-31 | L00193 | =P | C | | D06028P | 4 | DL | | 050-099 | | |
| 007 | 18 | PA | | 8-0 | 33-22-31 | L00193 | =P | C | | D06028P | 4 | DL | | 275-299 | | |
| 008 | 18 | PA | | 4-0 | 33-22-31 | L00192 | =G | C | * | L00193 | =G | C | | 050-099 | | |
| 008 | 18 | PA | | 7-0 | 33-22-31 | L00192 | =G | C | * | D06028P | 3 | DL | | 275-299 | | |
| 009 | 22 | PA | | 8-0 | 23-42-11 | D05331P | 1 | | | L00406 | =P | \$ | | 275-299 | | |
| 010 | 20 | PA | | 8-0 | 23-42-11 | D05331P | 4 | | | L00406 | =G | \$ | | 275-299 | | |
| 011 | 22 | PA | | 4-0 | 33-22-42 | L00220 | =G | E | * | D01770 | 8 | | | 275-299 | | |
| 012 | 22 | PA | | 8-0 | 23-34-13 | D05331P | 2 | | | L00409 | =P | \$ | | 275-299 | | |
| 013 | 22 | PA | | 8-0 | 33-25-11 | D05331P | 3 | | | L00407 | =P | \$ | | 050-099, 275-299 | | |
| 014 | 22 | PA | | 8-0 | 33-25-11 | D05331P | 6 | | | L00408 | =P | \$ | | 050-099, 275-299 | | |
| 018 | 22 | PA | | 7-0 | 23-34-13 | D05331P | 11 | | | B00146 | HI | C | | 275-299 | | |
| 023 | 24 | PK | | 7-0 | 23-42-12 | D05331P | 16 | | | B00146 | H/L | C | | 275-299 | | |
| 027 | 22 | PA | | 4-0 | 33-22-42 | L00220 | =G | E | * | D10676 | 8 | | | 275-299 | | |
| 030 | 22 | PA | | 2-2 | 33-22-42 | D01770 | 7 | | | SM00003 | 9 | | | 275-299 | | |
| 031 | 22 | PA | | 4-0 | 33-22-42 | D01768 | 11 | | | L00220 | =3 | C | | 275-299 | | |
| 032 | 22 | PA | | 4-0 | 33-22-42 | D01768 | 9 | | | L00220 | =1 | C | | 275-299 | | |
| 033 | 22 | PA | | 4-0 | 33-22-42 | D01768 | 10 | | | L00220 | =2 | C | | 275-299 | | |
| 034 | 22 | PA | | 4-0 | 33-22-42 | D01768 | 12 | | | L00220 | =4 | C | | 275-299 | | |
| 035 | 22 | PA | | 2-5 | 33-22-42 | D01768 | 7 | | | SM00003 | 9 | | | 275-299 | | |
| 036 | 22 | PA | | 5-1 | 33-22-42 | SM00003 | | 9 | | D06148P | 3 | | | 275-299 | | |
| 037 | 22 | PA | | 7-10 | 33-22-42 | L00220 | =G | E | * | D06148P | 1 | | | 275-299 | | |
| 038 | 22 | PA | | 2-0 | 33-22-42 | D01770 | 5 | | | SM00007 | 9 | | | 275-299 | | |
| 039 | 22 | PA | | 7-0 | 33-22-42 | D01768 | 5 | | | D06148P | 2 | | | 275-299 | | |
| 050 | 22 | PA | | 4-0 | 33-22-42 | D01768 | 8 | | | L00220 | =G | E | * | 275-299 | | |
| 055 | 20 | PA | | 7-0 | 23-42-12 | D05331P | 14 | | | B00145 | GRD | C | | 275-299 | | |
| 056 | 22 | PQ | C | 7-0 | 23-42-12 | D05331P | 13 | | | B00145 | 28V | C | | 275-299 | | |
| 056Z | | | C | 0-0 | 23-42-12 | D05331P | DED | | | B00145 | DED | | | 275-299 | | |
| 057 | 24 | PK | | 7-0 | 23-42-12 | D05331P | 12 | | | B00145 | H/L | C | | 275-299 | | |
| 058 | 22 | PQ | D | 7-0 | 23-42-12 | D05331P | 17 | | | B00146 | 28V | C | | 275-299 | | |
| 058Z | | | D | 0-0 | 23-42-12 | D05331P | DED | | | B00146 | DED | | | 275-299 | | |
| 059 | 20 | PA | | 7-0 | 23-42-12 | D05331P | 18 | | | B00146 | GRD | C | | 275-299 | | |
| 060 | 22 | PA | | 7-0 | 23-34-13 | D05331P | 15 | | | B00145 | HI | C | | 275-299 | | |
| 066 | 22 | PA | | 2-4 | 33-22-42 | D10676 | 7 | | | SM00003 | 9 | | | 275-299 | | |
| 067 | 22 | PA | | 6-0 | 33-22-42 | D06148P | 5 | | | SM00007 | 9 | | | 275-299 | | |
| 068 | 22 | PA | | 2-0 | 33-22-42 | D10676 | 5 | | | SM00007 | 9 | | | 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 1

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|---------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0110 | 286T0110 | | | AFT MID CABIN MOD (I) (continued) | | | | | | | | | | | |
| 069 | 22 | | PA | | 8-0 | 23-34-13 | D05331P | | 5 | | L00410 | =P | \$ | | 275-299 |
| 075 | 22 | | PA | | 7-0 | 23-42-11 | D05331P | | 1 | | L00406 | =P | \$ | | 050-099 |
| 076 | 20 | | PA | | 7-0 | 23-42-11 | D05331P | | 4 | | L00406 | =G | \$ | | 050-099 |
| 077 | 22 | | PA | | 8-0 | 23-34-13 | D05331P | | 12 | | L00410 | =P | \$ | | 050-099 |
| 100 | 20 | | PA | | 6-0 | 33-22-41 | L00231 | | =G | C | * | D06148P | 1 | | 050-099 |
| 100 | 20 | | PA | | 4-0 | 33-22-41 | L00231 | | =G | C | * | D06148P | 1 | | 150-199 |
| 101 | 20 | | PA | | 6-0 | 33-22-41 | L00231 | | =P | C | * | D06148P | 2 | | 050-099 |
| 101 | 20 | | PA | | 4-0 | 33-22-41 | L00231 | | =P | C | * | D06148P | 2 | | 150-199 |
| 102 | 22 | | PA | | 5-0 | 33-22-41 | L00231 | | =P | C | * | L00230 | =P | C | 050-099 |
| 102 | 22 | | PA | | 4-0 | 33-22-41 | L00231 | | =P | C | * | L00230 | =P | C | 150-199 |
| 103 | 22 | | PA | | 5-0 | 33-22-41 | L00231 | | =G | C | * | L00230 | =G | C | 050-099 |
| 103 | 22 | | PA | | 4-0 | 33-22-41 | L00231 | | =G | C | * | L00230 | =G | C | 150-199 |
| 104 | 22 | | PA | | 8-0 | 23-34-13 | D05331P | | 11 | | L00409 | =P | \$ | | 050-099 |
| 201B | 22 | | PB | AB | 8-0 | 23-31-14 | D05331P | | 7 | | B00075 | - | X | | 050-099 |
| 201R | 22 | | PB | AB | 0-0 | 23-31-14 | SM00001 | | | S | B00075 | + | X | | 050-099 |
| 202B | 22 | | PB | AC | 8-0 | 23-31-14 | SM00001 | | | S | B00074 | - | X | | 050-099 |
| 202R | 22 | | PB | AC | 0-0 | 23-31-14 | D05331P | | 8 | | B00074 | + | X | | 050-099 |
| 203B | 22 | | PB | AA | 8-0 | 23-31-14 | D05331P | | 8 | | B00243 | COM | Z | | 275-299 |
| 203R | 22 | | PB | AA | 0-0 | 23-31-14 | D05331P | | 7 | | B00243 | 4K | Z | | 275-299 |
| C-A | | | | | 0-0 | 33-22-42 | L00222 | | | BLK | D10676 | 12 | | | 275-299 |
| C-B | | | | | 0-0 | 33-22-42 | L00222 | | | BLK | D10676 | 11 | | | 275-299 |
| C-C | | | | | 0-0 | 33-22-42 | L00222 | | | WHT | D10676 | 9 | | | 275-299 |
| C-D | | | | | 0-0 | 33-22-42 | L00222 | | | WHT | D10676 | 10 | | | 275-299 |
| D-A | | | | | 0-0 | 33-22-42 | L00221 | | | BLK | D01770 | 12 | | | 275-299 |
| D-B | | | | | 0-0 | 33-22-42 | L00221 | | | BLK | D01770 | 11 | | | 275-299 |
| D-C | | | | | 0-0 | 33-22-42 | L00221 | | | WHT | D01770 | 9 | | | 275-299 |
| D-D | | | | | 0-0 | 33-22-42 | L00221 | | | WHT | D01770 | 10 | | | 275-299 |
| W0111 | 286T0111 | | | E1-1 SHELF | | | | | | | | | | | |
| 001 | 22 | | PA | | 3-0 | 27-11-12 | D00665A | | A08 | | D05549J | 18 | | | ALL |
| 002 | 22 | | PA | | 3-0 | 27-11-12 | D00665A | | A07 | | D05549J | 17 | | | ALL |
| 003 | 22 | | PA | | 4-0 | 27-09-14 | D05549J | | 4 | | TB0101G | 62 | 2 | | ALL |
| 004 | 22 | | PA | | 4-0 | 27-21-12 | D05403J | | 35 | | TB0101G | 69 | 2 | | ALL |
| 005 | 22 | | PA | | 5-0 | 27-21-12 | TB0101G | | 69 | 2 | D01263B | D04 | | | ALL |
| 006 | 22 | | PA | | 4-0 | 27-21-12 | TB0101G | | 69 | 2 | D05549J | 30 | | | ALL |
| 007 | 22 | | PA | | 4-0 | 27-09-14 | D05549J | | 22 | | TB0101H | 77 | 2 | | ALL |
| 011 | 22 | | PA | | 5-0 | 27-61-14 | D01251B | | G01 | | D01253B | E01 | | | ALL |
| 015 | 22 | | PQ | AO | 5-0 | 27-61-14 | D00825A | | A15 | | TB0101H | 81 | 2 | | ALL |
| 015Z | | | | AO | 0-0 | 27-61-14 | D00825A | | DED | | TB0101H | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 2

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0111 | 286T0111 | | | | E1-1 SHELF (continued) | | | | | | | | | | | | |
| 017 | 22 | | PA | | 3-0 | 27-61-14 | TB0101H | 171 | 2 | | D01253B | C01 | | | | | ALL |
| 019 | 22 | | PA | | 3-0 | 27-61-14 | D00825B | G06 | | | D01251A | C14 | | | | | ALL |
| 020 | 22 | | PA | | 3-0 | 27-61-14 | D00825B | G04 | | | D01251A | K12 | | | | | ALL |
| 022 | 22 | | PA | | 5-0 | 27-61-14 | D00825B | F06 | | | D01253A | C14 | | | | | ALL |
| 023 | 22 | | PA | | 5-0 | 27-61-14 | D00825B | F04 | | | D01253A | K12 | | | | | ALL |
| 030 | 22 | | PQ | BE | 5-0 | 27-61-15 | D00827A | A15 | | | TB0101H | 81 | 2 | | | | ALL |
| 030Z | | | | BE | 0-0 | 27-61-15 | D00827A | DED | | | TB0101H | DED | | | | | ALL |
| 033 | 22 | | PA | | 3-0 | 27-61-15 | D00827B | G14 | | | D01251A | C15 | | | | | ALL |
| 034 | 22 | | PA | | 3-0 | 27-61-15 | D00827B | G12 | | | D01251A | K13 | | | | | ALL |
| 035 | 22 | | PA | | 4-0 | 27-61-15 | D00827B | F14 | | | D01253A | C15 | | | | | ALL |
| 036 | 22 | | PA | | 4-0 | 27-61-15 | D00827B | F12 | | | D01253A | K13 | | | | | ALL |
| 039 | 22 | | PA | | 5-0 | 27-61-16 | D01251A | F13 | | | D00829A | E11 | | | | | ALL |
| 041 | 22 | | PA | | 5-0 | 27-61-16 | D01251A | J12 | | | D00829A | G03 | | | | | ALL |
| 042 | 22 | | PA | | 5-0 | 27-61-16 | D01251A | B14 | | | D00829A | G05 | | | | | ALL |
| 046 | 22 | | PA | | 1-0 | 27-61-16 | D00829A | A08 | | | D00829A | C07 | | | | | ALL |
| 047 | 22 | | PQ | BV | 3-0 | 27-61-16 | D00829A | A15 | | | TB0101H | 81 | 2 | | | | ALL |
| 047Z | | | | BV | 0-0 | 27-61-16 | D00829A | DED | | | TB0101H | DED | | | | | ALL |
| 050 | 22 | | PA | | 3-0 | 27-61-16 | D00829A | F05 | | | D01253A | B14 | | | | | ALL |
| 051 | 22 | | PA | | 3-0 | 27-61-16 | D00829A | F03 | | | D01253A | J12 | | | | | ALL |
| 055 | 22 | | PA | | 1-0 | 27-61-14 | D00825B | D06 | | | D00825B | D07 | | | | | ALL |
| 056 | 22 | | PA | | 1-0 | 27-61-14 | D00825B | B06 | | | D00825B | B07 | | | | | ALL |
| 063 | 22 | | PA | | 1-0 | 27-61-15 | D00827B | D14 | | | D00827B | D15 | | | | | ALL |
| 064 | 22 | | PA | | 1-0 | 27-61-15 | D00827B | B14 | | | D00827B | B15 | | | | | ALL |
| 065 | 22 | | PA | | 1-0 | 27-61-16 | D00829A | D05 | | | D00829A | D06 | | | | | ALL |
| 066 | 22 | | PA | | 1-0 | 27-61-16 | D00829A | B05 | | | D00829A | B06 | | | | | ALL |
| 069 | 22 | | PQ | CS | 3-0 | 27-09-11 | D05493J | | 2 | | D01253B | E15 | | | | | ALL |
| 069Z | | | | CS | 0-0 | 27-09-11 | D05493J | DED | | | D01253B | DED | | | | | ALL |
| 071 | 22 | | PQ | CU | 3-0 | 27-09-11 | D05493J | | 1 | | TB0101H | 81 | 2 | | | | ALL |
| 071Z | | | | CU | 0-0 | 27-09-11 | D05493J | DED | | | TB0101H | DED | | | | | ALL |
| 072 | 22 | | PQ | CV | 5-0 | 27-09-11 | D01251B | A15 | | | TB0101H | 81 | 2 | | | | ALL |
| 072Z | | | | CV | 0-0 | 27-09-11 | D01251B | DED | | | TB0101H | DED | | | | | ALL |
| 073 | 22 | | PQ | CW | 3-0 | 27-09-11 | D01253B | A15 | | | TB0101H | 81 | 2 | | | | ALL |
| 073Z | | | | CW | 0-0 | 27-09-11 | D01253B | DED | | | TB0101H | DED | | | | | ALL |
| 075 | 22 | | PA | | 4-0 | 27-09-12 | D05549J | | 11 | | TB0101H | 181 | 2 | | | | ALL |
| 076 | 22 | | PA | | 5-0 | 27-09-12 | D00825B | D02 | | | TB0101H | 181 | 2 | | | | ALL |
| 077 | 22 | | PA | | 5-0 | 27-09-12 | D00827B | D10 | | | TB0101H | 181 | 2 | | | | ALL |
| 078 | 22 | | PA | | 3-0 | 27-09-12 | D00829A | D01 | | | TB0101H | 181 | 2 | | | | ALL |
| 079 | 22 | | PA | | 4-0 | 27-09-12 | D00665A | E14 | | | TB0101H | 181 | 2 | | | | ALL |
| 080 | 22 | | PA | | 4-0 | 27-09-12 | D01259B | H04 | | | TB0101H | 181 | 2 | | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0110
Page 3
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0111 | 286T0111 | | | E1-1 SHELF (continued) | | | | | | | | | | | | |
| 081 | 22 | | PA | 5-0 | 27-09-12 | D01263B | D07 | | | | TB0101H | 181 | 2 | | ALL | |
| 082 | 22 | | PA | 2-0 | 27-09-13 | D01263B | A03 | | | | GD0004 | D.. | 2 | | 050-099, 150-199, 275-278 280-299 | |
| 082 | 22 | | PA | 6-0 | 27-09-13 | D01263B | A03 | | | | TB0101G | 179 | 2 | | ALL | |
| 083 | 22 | | PA | 6-0 | 27-09-13 | D01263B | B03 | | | | TB0101G | 180 | 2 | | ALL | |
| 084 | 22 | | PA | 4-0 | 27-09-13 | D00665B | H05 | | | | TB0101G | 180 | 2 | | ALL | |
| 085 | 22 | | PA | 4-0 | 27-09-13 | D00665B | H06 | | | | TB0101G | 179 | 2 | | ALL | |
| 086 | 22 | | PA | 4-0 | 27-09-13 | D05549J | 12 | | | | TB0101G | 180 | 2 | | ALL | |
| 087 | 22 | | PA | 4-0 | 27-09-13 | D05549J | 13 | | | | TB0101G | 179 | 2 | | ALL | |
| 088 | 22 | | PA | 5-0 | 27-09-13 | D00825A | A12 | | | | GD0012 | D.. | 2 | | ALL | |
| 089 | 22 | | PA | 4-0 | 27-09-14 | D05549J | 45 | | | | TB0101G | 62 | 2 | | ALL | |
| 090 | 22 | | PA | 5-0 | 27-21-12 | D01263B | D13 | | | | D01253A | H13 | | | ALL | |
| 091 | 22 | | PA | 5-0 | 27-21-12 | D01263B | A13 | | | | D01253A | A15 | | | ALL | |
| 092 | 22 | | PA | 3-0 | 27-09-13 | D00829A | A12 | | | | GD0012 | D.. | 2 | | ALL | |
| 093 | 22 | | PA | 4-0 | 27-09-13 | D00827A | A12 | | | | GD0012 | D.. | 2 | | ALL | |
| 094 | 22 | | PA | 3-0 | 27-21-12 | D01263B | D12 | | | | D01251A | H13 | | | ALL | |
| 095 | 22 | | PA | 3-0 | 27-21-12 | D01263B | A12 | | | | D01251A | A15 | | | ALL | |
| 096 | 22 | | PA | 4-0 | 27-09-14 | D05549J | 46 | | | | TB0101G | 76 | 2 | | ALL | |
| 097 | 22 | | PA | 5-0 | 27-09-14 | D01251B | A13 | | | | TB0101G | 76 | 2 | | ALL | |
| 098 | 22 | | PA | 5-0 | 27-09-14 | D01263A | C15 | | | | TB0101G | 62 | 2 | | ALL | |
| 101 | 22 | | PA | 3-0 | 27-09-14 | D00829A | C13 | | | | TB0101H | 77 | 2 | | ALL | |
| 102 | 22 | | PA | 5-0 | 27-09-14 | D00827A | C13 | | | | TB0101H | 77 | 2 | | ALL | |
| 103 | 22 | | PA | 5-0 | 27-09-14 | D00825A | C13 | | | | TB0101H | 77 | 2 | | ALL | |
| 104 | 22 | | PA | 4-0 | 27-09-14 | D01253B | A13 | | | | TB0101G | 76 | 2 | | ALL | |
| 105 | 22 | | PA | 4-0 | 27-61-11 | D05549J | 20 | | | | TB0101G | 176 | 2 | | ALL | |
| 106 | 22 | | PA | 5-0 | 27-61-11 | D00825B | E02 | | | | TB0101G | 176 | 2 | | ALL | |
| 107 | 22 | | PA | 5-0 | 27-61-11 | D00827B | E10 | | | | TB0101G | 176 | 2 | | ALL | |
| 108 | 22 | | PA | 3-0 | 27-61-11 | D00829A | E01 | | | | TB0101G | 176 | 2 | | ALL | |
| 109 | 22 | | PA | 4-0 | 27-61-12 | D05549J | 21 | | | | TB0101G | 75 | 2 | | ALL | |
| 110 | 22 | | PA | 3-0 | 27-61-12 | D00829A | B13 | | | | TB0101G | 75 | 2 | | ALL | |
| 111 | 22 | | PA | 5-0 | 27-61-12 | D00827A | B13 | | | | TB0101G | 75 | 2 | | ALL | |
| 112 | 22 | | PA | 5-0 | 27-61-12 | D00825A | B13 | | | | TB0101G | 75 | 2 | | ALL | |
| 113 | 22 | | PA | 4-0 | 27-21-12 | D01263A | B15 | | | | D05549J | 37 | | | ALL | |
| 114 | 22 | | PA | 4-0 | 27-21-12 | D01263A | D15 | | | | D05549J | 38 | | | ALL | |
| 115 | 22 | | PA | 4-0 | 27-21-12 | D01263A | A15 | | | | D05549J | 39 | | | ALL | |
| 116 | 22 | | PA | 4-0 | 27-21-12 | D01263B | C08 | | | | D05549J | 31 | | | ALL | |
| 117 | 22 | | PA | 5-0 | 27-21-12 | D01253A | A10 | | | | D01251A | C10 | | | ALL | |
| 118 | 22 | | PA | 4-0 | 27-21-12 | D01253A | C12 | | | | TB0101H | 167 | 2 | | ALL | |
| 121 | 22 | | PA | 4-0 | 27-21-12 | D01263B | D08 | | | | D00665A | K15 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 4

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|-------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0111 | 286T0111 | | | E1-1 SHELF (continued) | | | | | | | | | | | |
| 122 | 22 | PA | | | 4-0 | 22-21-11 | D01259B | | C02 | | D01253A | J13 | | | ALL |
| 124 | 22 | PA | | | 4-0 | 22-21-11 | D01259B | | A02 | | D01253A | B15 | | | ALL |
| 126 | 22 | PA | | | 4-0 | 22-21-11 | D01259B | | A01 | | D01251A | B15 | | | ALL |
| 127 | 22 | PA | | | 4-0 | 22-21-11 | D01259B | | C01 | | D01251A | J13 | | | ALL |
| 130 | 22 | PA | | | 4-0 | 22-21-11 | D01259B | | H05 | | D05549J | 3 | | | ALL |
| 131 | 22 | PQ | FF | | 4-0 | 22-21-11 | D01259B | | A04 | | TB0101H | 81 | 2 | | ALL |
| 131Z | | | FF | | 0-0 | 22-21-11 | D01259B | | DED | | TB0101H | DED | | | ALL |
| 132 | 22 | PA | | | 3-0 | 22-21-11 | D05549J | | 1 | | D01259B | K07 | | | ALL |
| 133 | 22 | PA | | | 3-0 | 22-21-11 | D05549J | | 2 | | D01259B | K08 | | | ALL |
| 145 | 22 | PA | | | 3-0 | 22-24-11 | D05549J | | 9 | | D00665A | C11 | | | ALL |
| 146 | 22 | PA | | | 3-0 | 22-24-11 | D05549J | | 10 | | D00665A | A09 | | | ALL |
| 147 | 22 | PA | | | 3-0 | 22-24-11 | D00665A | | C14 | | D05549J | 8 | | | ALL |
| 148 | 22 | PA | | | 4-0 | 27-41-11 | D05549J | | 15 | | TB0101G | 177 | 2 | | ALL |
| 149 | 22 | PA | | | 4-0 | 27-41-11 | D05549J | | 16 | | TB0101G | 178 | 2 | | ALL |
| 150 | 22 | PA | | | 4-0 | 27-41-11 | D05549J | | 23 | | TB0101G | 164 | 2 | | ALL |
| 151 | 22 | PA | | | 3-0 | 27-41-11 | D05403J | | 25 | | D00665A | C08 | | | ALL |
| 152 | 22 | PA | | | 3-0 | 27-41-11 | D05403J | | 26 | | D00665A | C07 | | | ALL |
| 153 | 22 | PA | | | 4-0 | 27-41-11 | TB0101G | | 164 | 2 | D00665A | C09 | | | ALL |
| 154 | 22 | PA | | | 3-0 | 27-41-11 | D05403J | | 27 | | TB0101G | 164 | 2 | | ALL |
| 155 | 22 | PA | | | 4-0 | 27-41-11 | D00665A | | A13 | | TB0101G | 177 | 2 | | ALL |
| 156 | 22 | PA | | | 3-0 | 27-41-11 | D05133J | | 11 | | TB0101G | 177 | 2 | | ALL |
| 157 | 22 | PA | | | 4-0 | 27-41-11 | D00665A | | A14 | | TB0101G | 178 | 2 | | ALL |
| 158 | 22 | PA | | | 4-0 | 27-41-11 | D05133J | | 10 | | TB0101G | 178 | 2 | | ALL |
| 159 | 22 | PA | | | 3-0 | 27-41-11 | D00665A | | C12 | | D05549J | 19 | | | ALL |
| 160 | 22 | PA | | | 4-0 | 27-41-11 | D00665A | | G13 | | D01251A | H12 | | | ALL |
| 161 | 22 | PA | | | 4-0 | 27-41-11 | D00665A | | G14 | | D01251A | A14 | | | ALL |
| 163 | 22 | PA | | | 5-0 | 27-41-11 | D00665A | | J13 | | D01253A | H12 | | | ALL |
| 164 | 22 | PA | | | 5-0 | 27-41-11 | D00665A | | J14 | | D01253A | A14 | | | ALL |
| 167 | 22 | PA | | | 1-0 | 27-61-16 | D00829A | | D02 | | D00829A | C02 | | | ALL |
| 170 | 22 | PA | | | 3-0 | 22-22-11 | D00665B | | E05 | | D05549J | 7 | | | ALL |
| 181 | 22 | PA | | | 4-0 | 27-09-14 | D05549J | | 47 | | TB0101H | 77 | 2 | | ALL |
| 184 | 22 | PA | | | 3-0 | 22-21-11 | D01259A | | H15 | | D04981J | 3 | | | 150-199, 275-299 |
| 187 | 22 | PA | | | 3-0 | 27-61-16 | D01253A | | F13 | | D00829A | E12 | | | ALL |
| 188 | 22 | PA | | | 4-0 | 22-21-11 | D01259A | | F15 | | D05403J | 17 | | | ALL |
| 189 | 22 | PA | | | 3-0 | 27-41-11 | D05549J | | 42 | | D00665A | B13 | | | ALL |
| 190 | 22 | PA | | | 3-0 | 27-41-11 | D05549J | | 43 | | D00665A | B14 | | | ALL |
| 191 | 22 | PA | | | 4-0 | 27-61-16 | D00829A | | C01 | | D00665A | A15 | | | ALL |
| 192 | 22 | PA | | | 3-0 | 27-61-15 | D00827B | | H12 | | D05549J | 40 | | | ALL |
| 193 | 20 | PA | | | 3-0 | 27-61-15 | GDX0006 | | D.. | 2 | D05549J | 41 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0110
 Page 5
 Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0111 | 286T0111 | | | E1-1 SHELF (continued) | | | | | | | | | | | | |
| 201B | 22 | PB | IA | 4-0 | 27-21-12 | D05403J | | 34 | | | | TB0101G | 68 | 2 | | ALL |
| 201R | 22 | PB | IA | 0-0 | 27-21-12 | D05403J | | 33 | | | | TB0101G | 67 | 2 | | ALL |
| 202B | 22 | PB | IB | 5-0 | 27-21-12 | D01263B | | A10 | | | | TB0101G | 68 | 2 | | ALL |
| 202R | 22 | PB | IB | 0-0 | 27-21-12 | D01263B | | A09 | | | | TB0101G | 67 | 2 | | ALL |
| 203B | 22 | PB | IC | 4-0 | 27-21-12 | D05549J | | 36 | | | | TB0101G | 68 | 2 | | ALL |
| 203R | 22 | PB | IC | 0-0 | 27-21-12 | D05549J | | 35 | | | | TB0101G | 67 | 2 | | ALL |
| 205B | 22 | PB | IE | 4-0 | 27-61-14 | D05133J | | 9 | | | | TB0101H | 171 | 2 | | ALL |
| 205R | 22 | PB | IE | 0-0 | 27-61-14 | D05133J | | 8 | | | | TB0101H | 169 | 2 | | ALL |
| 206B | 22 | PB | IF | 4-0 | 27-61-14 | D05133J | | 2 | | | | TB0101H | 171 | 2 | | ALL |
| 206R | 22 | PB | IF | 0-0 | 27-61-14 | D05133J | | 1 | | | | TB0101H | 169 | 2 | | ALL |
| 207B | 22 | PB | IG | 5-0 | 27-61-14 | D01251B | | C01 | | | | TB0101H | 171 | 2 | | ALL |
| 207R | 22 | PB | IG | 0-0 | 27-61-14 | D01251B | | A01 | | | | TB0101H | 169 | 2 | | ALL |
| 208B | 22 | PB | IH | 5-0 | 27-61-14 | D00825B | | J07 | | | | TB0101H | 171 | 2 | | ALL |
| 208R | 22 | PB | IH | 0-0 | 27-61-14 | D00825B | | K07 | | | | TB0101H | 169 | 2 | | ALL |
| 209B | 22 | PB | II | 4-0 | 27-61-15 | D00827B | | J15 | | | | TB0101H | 171 | 2 | | ALL |
| 209R | 22 | PB | II | 0-0 | 27-61-15 | D00827B | | K15 | | | | TB0101H | 169 | 2 | | ALL |
| 210B | 22 | PB | IJ | 4-0 | 27-61-16 | D05403J | | 3 | | | | D00829A | G08 | | | ALL |
| 210R | 22 | PB | IJ | 0-0 | 27-61-16 | D05403J | | 1 | | | | D00829A | G09 | | | ALL |
| 211B | 22 | PB | IK | 3-0 | 27-61-16 | TB0101G | | 71 | 2 | | | D00829A | J11 | | | ALL |
| 211R | 22 | PB | IK | 0-0 | 27-61-16 | TB0101G | | 70 | 2 | | | D00829A | K11 | | | ALL |
| 212B | 22 | PB | IL | 4-0 | 27-61-16 | D05403J | | 11 | | | | D00829A | G11 | | | ALL |
| 212R | 22 | PB | IL | 0-0 | 27-61-16 | D05403J | | 10 | | | | D00829A | G10 | | | ALL |
| 213B | 22 | PB | IM | 4-0 | 27-61-16 | D05403J | | 9 | | | | TB0101G | 71 | 2 | | ALL |
| 213R | 22 | PB | IM | 0-0 | 27-61-16 | D05403J | | 8 | | | | TB0101G | 70 | 2 | | ALL |
| 214B | 22 | PB | IN | 4-0 | 27-61-16 | D05403J | | 15 | | | | TB0101G | 71 | 2 | | ALL |
| 214R | 22 | PB | IN | 0-0 | 27-61-16 | D05403J | | 14 | | | | TB0101G | 70 | 2 | | ALL |
| 215B | 22 | PB | IO | 3-0 | 27-61-16 | D00829A | | J06 | | | | TB0101H | 171 | 2 | | ALL |
| 215R | 22 | PB | IO | 0-0 | 27-61-16 | D00829A | | K06 | | | | TB0101H | 169 | 2 | | ALL |
| 216 | 20 | UA | | 0-18 | 22-21-11 | GDX0007 | | S.. | 2 | | | D05549J | | | FE | ALL |
| 216B | 24 | PW | IP | 3-0 | 22-21-11 | D01259B | | K05 | | | | D05549J | 25 | | | ALL |
| 216R | 24 | PW | IP | 0-0 | 22-21-11 | D01259B | | K04 | | | | D05549J | 24 | | | ALL |
| 216Z | | | IP | 0-0 | 22-21-11 | D01259B | | DED | | | | D05549J | | | FE | ALL |
| 217B | 24 | PW | IQ | 4-0 | 22-21-11 | D01259A | | A15 | | | | TB0101G | 80 | 2 | | ALL |
| 217R | 24 | PW | IQ | 0-0 | 22-21-11 | D01259A | | A14 | | | | TB0101G | 79 | 2 | | ALL |
| 217Z | | | IQ | 0-0 | 22-21-11 | D01259A | | DED | | | | TB0101G | | | FC | ALL |
| 218B | 22 | PB | IR | 3-0 | 22-21-11 | D01259A | | D15 | | | | D05403J | 19 | | | ALL |
| 218R | 22 | PB | IR | 0-0 | 22-21-11 | D01259A | | E14 | | | | D05403J | 18 | | | ALL |
| 219B | 22 | PB | IS | 3-0 | 22-21-11 | D01259A | | E15 | | | | TB0101H | 167 | 2 | | ALL |
| 219R | 22 | PB | IS | 0-0 | 22-21-11 | D01259A | | F14 | | | | TB0101H | 165 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 6

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0111 | 286T0111 | | | E1-1 SHELF (continued) | | | | | | | | | | | |
| 220B | 22 | PB | IT | | 4-0 | 22-21-11 | D05403J | | 24 | | TB0101H | 167 | 2 | | ALL |
| 220R | 22 | PB | IT | | 0-0 | 22-21-11 | D05403J | | 23 | | TB0101H | 165 | 2 | | ALL |
| 221B | 24 | PW | IU | | 4-0 | 27-11-12 | D00665A | | A12 | | TB0101G | 80 | 2 | | ALL |
| 221R | 24 | PW | IU | | 0-0 | 27-11-12 | D00665A | | A11 | | TB0101G | 79 | 2 | | ALL |
| 221Z | | | IU | | 0-0 | 27-11-12 | D00665A | | DED | | TB0101G | | | FC | ALL |
| 222 | 20 | UA | | | 0-18 | 27-11-12 | D05549J | | | FF | GDY0007 | S.. | 2 | | ALL |
| 222B | 24 | PW | IV | | 4-0 | 27-11-12 | D05549J | | 28 | | TB0101G | 80 | 2 | | ALL |
| 222R | 24 | PW | IV | | 0-0 | 27-11-12 | D05549J | | 27 | | TB0101G | 79 | 2 | | ALL |
| 222Z | | | IV | | 0-0 | 27-11-12 | D05549J | | | FF | TB0101G | | | FC | ALL |
| 223B | 22 | PB | IW | | 5-0 | 27-21-12 | D01251A | | C12 | | TB0101H | 167 | 2 | | ALL |
| 223R | 22 | PB | IW | | 0-0 | 27-21-12 | D01251A | | A12 | | TB0101H | 165 | 2 | | ALL |
| 224B | 22 | PB | IX | | 4-0 | 27-21-12 | D05403J | | 29 | | TB0101H | 167 | 2 | | ALL |
| 224R | 22 | PB | IX | | 0-0 | 27-21-12 | D05403J | | 28 | | TB0101H | 165 | 2 | | ALL |
| 225B | 22 | PB | IY | | 5-0 | 27-21-12 | D01263A | | A10 | | TB0101H | 167 | 2 | | ALL |
| 225R | 22 | PB | IY | | 0-0 | 27-21-12 | D01263A | | A09 | | TB0101H | 165 | 2 | | ALL |
| 226B | 22 | PB | JA | | 5-0 | 27-21-12 | D01263B | | A05 | | TB0101H | 167 | 2 | | ALL |
| 226R | 22 | PB | JA | | 0-0 | 27-21-12 | D01263B | | A04 | | TB0101H | 165 | 2 | | ALL |
| 227B | 22 | PB | JB | | 3-0 | 27-21-12 | D01263B | | D10 | | D00665A | K14 | | | ALL |
| 227R | 22 | PB | JB | | 0-0 | 27-21-12 | D01263B | | D09 | | D00665A | K13 | | | ALL |
| 228B | 22 | PB | JC | | 4-0 | 22-21-11 | D01259A | | H12 | | D04981J | 1 | | | 150-199, 275-299 |
| 228R | 22 | PB | JC | | 0-0 | 22-21-11 | D01259A | | K12 | | D04981J | 2 | | | 150-199, 275-299 |
| 229 | 20 | UA | | | 1-6 | 22-21-11 | D04981J | | | JD | GDY0006 | S.. | 2 | | 150-199, 275-299 |
| 229B | 22 | PR | JD | | 3-0 | 22-21-11 | D01259B | | K15 | | D04981J | 5 | | | 150-199, 275-299 |
| 229R | 22 | PR | JD | | 0-0 | 22-21-11 | D01259B | | K14 | | D04981J | 4 | | | 150-199, 275-299 |
| 229Z | | | JD | | 0-0 | 22-21-11 | D01259B | | DED | | D04981J | | | JD | 150-199, 275-299 |
| 232 | 20 | UA | | | 1-6 | 22-21-31 | D01259B | | | JG | GDY0008 | S.. | 2 | | 150-199, 275-299 |
| 232B | 24 | PW | JG | | 3-0 | 22-21-31 | D05549J | | 34 | | D01259B | H15 | | | 150-199, 275-299 |
| 232R | 24 | PW | JG | | 0-0 | 22-21-31 | D05549J | | 32 | | D01259B | H14 | | | 150-199, 275-299 |
| 232Z | | | JG | | 0-0 | 22-21-31 | D05549J | | 50 | | D01259B | | | JG | 150-199, 275-299 |
| 301B | 22 | PC | MA | | 5-0 | 27-21-12 | D01263B | | B05 | | TB0101G | 65 | 2 | | ALL |
| 301R | 22 | PC | MA | | 0-0 | 27-21-12 | D01263B | | B06 | | TB0101G | 64 | 2 | | ALL |
| 301Y | 22 | PC | MA | | 0-0 | 27-21-12 | D01263B | | B04 | | TB0101G | 66 | 2 | | ALL |
| 302B | 22 | PC | MB | | 4-0 | 27-21-12 | D05403J | | 31 | | TB0101G | 65 | 2 | | ALL |
| 302R | 22 | PC | MB | | 0-0 | 27-21-12 | D05403J | | 30 | | TB0101G | 64 | 2 | | ALL |
| 302Y | 22 | PC | MB | | 0-0 | 27-21-12 | D05403J | | 32 | | TB0101G | 66 | 2 | | ALL |
| 303B | 22 | PC | MC | | 5-0 | 27-21-12 | D01263A | | B09 | | TB0101G | 65 | 2 | | ALL |
| 303R | 22 | PC | MC | | 0-0 | 27-21-12 | D01263A | | B08 | | TB0101G | 64 | 2 | | ALL |
| 303Y | 22 | PC | MC | | 0-0 | 27-21-12 | D01263A | | B10 | | TB0101G | 66 | 2 | | ALL |
| 304B | 22 | PC | MD | | 4-0 | 27-61-14 | D05133J | | 4 | | TB0101G | 73 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 7

Jan 21/2005



| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0111 | 286T0111 | | | E1-1 SHELF (continued) | | | | | | | | | | | |
| 304R | 22 | PC | MD | | 0-0 | 27-61-14 | D05133J | | 6 | | TB0101G | 72 | 2 | | ALL |
| 304Y | 22 | PC | MD | | 0-0 | 27-61-14 | D05133J | | 7 | | TB0101G | 74 | 2 | | ALL |
| 305B | 22 | PC | ME | | 4-0 | 27-61-14 | D05133J | | 15 | | TB0101G | 174 | 2 | | ALL |
| 305R | 22 | PC | ME | | 0-0 | 27-61-14 | D05133J | | 3 | | TB0101G | 173 | 2 | | ALL |
| 305Y | 22 | PC | ME | | 0-0 | 27-61-14 | D05133J | | 5 | | TB0101G | 175 | 2 | | ALL |
| 306B | 22 | PC | MF | | 5-0 | 27-61-14 | D00825B | | J06 | | TB0101G | 73 | 2 | | ALL |
| 306R | 22 | PC | MF | | 0-0 | 27-61-14 | D00825B | | J04 | | TB0101G | 72 | 2 | | ALL |
| 306Y | 22 | PC | MF | | 0-0 | 27-61-14 | D00825B | | J05 | | TB0101G | 74 | 2 | | ALL |
| 307B | 22 | PC | MG | | 5-0 | 27-61-14 | D00825B | | K06 | | TB0101G | 174 | 2 | | ALL |
| 307R | 22 | PC | MG | | 0-0 | 27-61-14 | D00825B | | K04 | | TB0101G | 173 | 2 | | ALL |
| 307Y | 22 | PC | MG | | 0-0 | 27-61-14 | D00825B | | K05 | | TB0101G | 175 | 2 | | ALL |
| 308B | 22 | PC | MH | | 5-0 | 27-61-15 | D00827B | | J14 | | TB0101G | 73 | 2 | | ALL |
| 308R | 22 | PC | MH | | 0-0 | 27-61-15 | D00827B | | J12 | | TB0101G | 72 | 2 | | ALL |
| 308Y | 22 | PC | MH | | 0-0 | 27-61-15 | D00827B | | J13 | | TB0101G | 74 | 2 | | ALL |
| 309B | 22 | PC | MI | | 5-0 | 27-61-15 | D00827B | | K14 | | TB0101G | 174 | 2 | | ALL |
| 309R | 22 | PC | MI | | 0-0 | 27-61-15 | D00827B | | K12 | | TB0101G | 173 | 2 | | ALL |
| 309Y | 22 | PC | MI | | 0-0 | 27-61-15 | D00827B | | K13 | | TB0101G | 175 | 2 | | ALL |
| 310B | 22 | PC | MJ | | 4-0 | 27-61-16 | D00829A | | K10 | | D05403J | 4 | | | ALL |
| 310R | 22 | PC | MJ | | 0-0 | 27-61-16 | D00829A | | K08 | | D05403J | 5 | | | ALL |
| 310Y | 22 | PC | MJ | | 0-0 | 27-61-16 | D00829A | | K09 | | D05403J | 7 | | | ALL |
| 311B | 22 | PC | MK | | 4-0 | 27-61-16 | D00829A | | J10 | | D05403J | 6 | | | ALL |
| 311R | 22 | PC | MK | | 0-0 | 27-61-16 | D00829A | | J08 | | D05403J | 12 | | | ALL |
| 311Y | 22 | PC | MK | | 0-0 | 27-61-16 | D00829A | | J09 | | D05403J | 13 | | | ALL |
| 312B | 22 | PC | ML | | 3-0 | 27-61-16 | D00829A | | J05 | | TB0101G | 73 | 2 | | ALL |
| 312R | 22 | PC | ML | | 0-0 | 27-61-16 | D00829A | | J03 | | TB0101G | 72 | 2 | | ALL |
| 312Y | 22 | PC | ML | | 0-0 | 27-61-16 | D00829A | | J04 | | TB0101G | 74 | 2 | | ALL |
| 313B | 22 | PC | MM | | 3-0 | 27-61-16 | D00829A | | K05 | | TB0101G | 174 | 2 | | ALL |
| 313R | 22 | PC | MM | | 0-0 | 27-61-16 | D00829A | | K03 | | TB0101G | 173 | 2 | | ALL |
| 313Y | 22 | PC | MM | | 0-0 | 27-61-16 | D00829A | | K04 | | TB0101G | 175 | 2 | | ALL |
| 314B | 22 | PC | MN | | 3-0 | 22-21-11 | D01259A | | C14 | | D05403J | 21 | | | ALL |
| 314R | 22 | PC | MN | | 0-0 | 22-21-11 | D01259A | | D14 | | D05403J | 20 | | | ALL |
| 314Y | 22 | PC | MN | | 0-0 | 22-21-11 | D01259A | | C15 | | D05403J | 22 | | | ALL |
| 315B | 22 | PC | MO | | 4-0 | 22-21-11 | D01259B | | K02 | | D01251A | K09 | | | ALL |
| 315R | 22 | PC | MO | | 0-0 | 22-21-11 | D01259B | | K01 | | D01251A | K08 | | | ALL |
| 315Y | 22 | PC | MO | | 0-0 | 22-21-11 | D01259B | | J01 | | D01251A | J08 | | | ALL |
| 316B | 22 | PC | MP | | 4-0 | 22-21-11 | D01259B | | H01 | | D01251A | J09 | | | ALL |
| 316R | 22 | PC | MP | | 0-0 | 22-21-11 | D01259B | | J02 | | D01251A | K10 | | | ALL |
| 316Y | 22 | PC | MP | | 0-0 | 22-21-11 | D01259B | | H02 | | D01251A | J10 | | | ALL |
| 317B | 22 | PC | MQ | | 3-0 | 22-21-11 | D01259B | | G02 | | D01253A | K09 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 8

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0111 | 286T0111 | | | E1-1 SHELF (continued) | | | | | | | | | | | |
| 317R | 22 | PC | MQ | | 0-0 | 22-21-11 | D01259B | G01 | | | D01253A | K08 | | | ALL |
| 317Y | 22 | PC | MQ | | 0-0 | 22-21-11 | D01259B | F01 | | | D01253A | J08 | | | ALL |
| 318B | 22 | PC | MR | | 3-0 | 22-21-11 | D01259B | E01 | | | D01253A | J09 | | | ALL |
| 318R | 22 | PC | MR | | 0-0 | 22-21-11 | D01259B | F02 | | | D01253A | K10 | | | ALL |
| 318Y | 22 | PC | MR | | 0-0 | 22-21-11 | D01259B | E02 | | | D01253A | J10 | | | ALL |
| 319B | 22 | PC | MS | | 4-0 | 27-41-11 | D00665B | K03 | | | D01251A | H09 | | | ALL |
| 319R | 22 | PC | MS | | 0-0 | 27-41-11 | D00665B | K02 | | | D01251A | H08 | | | ALL |
| 319Y | 22 | PC | MS | | 0-0 | 27-41-11 | D00665B | K04 | | | D01251A | G08 | | | ALL |
| 320B | 22 | PC | MT | | 4-0 | 27-41-11 | D00665B | J03 | | | D01251A | G09 | | | ALL |
| 320R | 22 | PC | MT | | 0-0 | 27-41-11 | D00665B | J02 | | | D01251A | H10 | | | ALL |
| 320Y | 22 | PC | MT | | 0-0 | 27-41-11 | D00665B | J04 | | | D01251A | G10 | | | ALL |
| 321B | 22 | PC | MU | | 4-0 | 27-41-11 | D00665B | H03 | | | D01253A | H09 | | | ALL |
| 321R | 22 | PC | MU | | 0-0 | 27-41-11 | D00665B | H02 | | | D01253A | H08 | | | ALL |
| 321Y | 22 | PC | MU | | 0-0 | 27-41-11 | D00665B | H04 | | | D01253A | G08 | | | ALL |
| 322B | 22 | PC | MV | | 4-0 | 27-41-11 | D00665B | G03 | | | D01253A | G09 | | | ALL |
| 322R | 22 | PC | MV | | 0-0 | 27-41-11 | D00665B | G02 | | | D01253A | H10 | | | ALL |
| 322Y | 22 | PC | MV | | 0-0 | 27-41-11 | D00665B | G04 | | | D01253A | G10 | | | ALL |
| FRA | | | | | 0-0 | 22-21-11 | D04981J | | | JD | D04981J | 7 | | | 150-199, 275-299 |
| FRE | | | | | 0-0 | 22-21-11 | D05549J | 26 | | | D05549J | | | FE | ALL |
| FRF | | | | | 0-0 | 27-11-12 | D05549J | 29 | | | D05549J | | | FF | ALL |
| W0114 | 286T0114 | | | FWD CABIN MID (L) | | | | | | | | | | | |
| 001 | 22 | PA | | | 5-0 | 33-22-41 | D01762 | 5 | | | D06062P | 1 | | | 050-099, 275-299 |
| 001 | 22 | PA | | | 4-0 | 33-22-41 | D06062P | 1 | | | D01762 | 5 | | | 150-199 |
| 003 | 22 | PA | | | 4-0 | 33-22-41 | L00215 | =G | E | * | D01762 | 8 | | | 050-099, 275-299 |
| 003 | 22 | PA | | | 3-0 | 33-22-41 | L00215 | =G | E | * | D01762 | 8 | | | 150-199 |
| 004 | 22 | PA | | | 4-0 | 33-22-41 | D01762 | 9 | | | L00215 | =1 | C | | 050-099, 275-299 |
| 004 | 22 | PA | | | 3-0 | 33-22-41 | L00215 | =1 | C | | D01762 | 9 | | | 150-199 |
| 005 | 22 | PA | | | 4-0 | 33-22-41 | D01762 | 10 | | | L00215 | =2 | C | | 050-099, 275-299 |
| 005 | 22 | PA | | | 3-0 | 33-22-41 | L00215 | =2 | C | | D01762 | 10 | | | 150-199 |
| 006 | 22 | PA | | | 4-0 | 33-22-41 | D01762 | 11 | | | L00215 | =3 | C | | 050-099, 275-299 |
| 006 | 22 | PA | | | 3-0 | 33-22-41 | L00215 | =3 | C | | D01762 | 11 | | | 150-199 |
| 007 | 22 | PA | | | 4-0 | 33-22-41 | D01762 | 12 | | | L00215 | =4 | C | | 050-099, 275-299 |
| 007 | 22 | PA | | | 3-0 | 33-22-41 | L00215 | =4 | C | | D01762 | 12 | | | 150-199 |
| 009 | 22 | PA | | | 5-0 | 33-22-41 | D01764 | 8 | | | L00215 | =G | E | * | 050-099, 275-299 |
| 009 | 22 | PA | | | 3-0 | 33-22-41 | L00215 | =G | E | * | D01764 | 8 | | | 150-199 |
| 014 | 22 | PA | | | 4-0 | 33-22-41 | D06062P | 5 | | | D01766 | 5 | | | ALL |
| 015 | 22 | PA | | | 3-0 | 33-22-41 | SP01086 | 9 | | | D01766 | 11 | | | ALL |
| 018 | 22 | PA | | | 4-0 | 33-22-41 | L00215 | =G | E | | D01766 | 8 | | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0110
Page 9
Jan 21/2005



| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | |
|--------------|-----------------|----|-------|--------------------------------------|----------|---------|---------|-------|------|---------|--------|-------|-------------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term |
| W0114 | 286T0114 | | | FWD CABIN MID (L) (continued) | | | | | | | | | | |
| 018 | 22 | PA | | 3-0 | 33-22-41 | L00215 | =G | E | * | D01766 | 8 | | | 150-199 |
| 018 | 22 | PA | | 4-0 | 33-22-41 | L00215 | =G | E | * | D01766 | 8 | | | 275-299 |
| 019 | 22 | PA | | 3-0 | 33-22-41 | SP01088 | | 9 | | D01766 | 12 | | | ALL |
| 022 | 22 | PA | | 5-0 | 33-22-41 | L00215 | =G | E | | D06062P | 7 | | | 050-099 |
| 022 | 22 | PA | | 4-0 | 33-22-41 | L00215 | =G | E | * | D06062P | 7 | | | 150-199 |
| 022 | 22 | PA | | 5-0 | 33-22-41 | L00215 | =G | E | * | D06062P | 7 | | | 275-299 |
| 024 | 22 | PA | | 5-0 | 33-22-41 | D01762 | | 7 | | D06062P | 11 | | | 050-099, 275-299 |
| 024 | 22 | PA | | 4-0 | 33-22-41 | D06062P | | 11 | | D01762 | 7 | | | 150-199 |
| 025 | 22 | PA | | 3-6 | 33-22-41 | D01764 | | 5 | | D06062P | 10 | | | 050-099, 275-299 |
| 025 | 22 | PA | | 4-0 | 33-22-41 | D06062P | | 10 | | D01764 | 5 | | | 150-199 |
| 026 | 22 | PA | | 3-6 | 33-22-41 | D01764 | | 7 | | D06062P | 9 | | | 050-099, 275-299 |
| 026 | 22 | PA | | 4-0 | 33-22-41 | D01764 | | 7 | | D06062P | 9 | | | 150-199 |
| 027 | 22 | PA | | 4-0 | 33-22-41 | D01766 | | 7 | | D06062P | 8 | | | ALL |
| B-A | | | | 0-0 | 33-22-41 | L00217 | BLK | | | SP01086 | | 9 | | ALL |
| B-B | | | | 0-0 | 33-22-41 | L00217 | BLK | | | SP01088 | | 9 | | ALL |
| B-C | | | | 0-0 | 33-22-41 | L00217 | WHT | | | D01766 | | 9 | | ALL |
| B-D | | | | 0-0 | 33-22-41 | L00217 | WHT | | | D01766 | 10 | | | ALL |
| C-A | | | | 0-0 | 33-22-41 | L00216 | BLK | | | D01764 | 9 | | | ALL |
| C-B | | | | 0-0 | 33-22-41 | L00216 | BLK | | | D01764 | 10 | | | ALL |
| C-C | | | | 0-0 | 33-22-41 | L00216 | WHT | | | D01764 | 11 | | | ALL |
| C-D | | | | 0-0 | 33-22-41 | L00216 | WHT | | | D01764 | 12 | | | ALL |
| E-A | | | | 0-0 | 33-22-41 | L00218 | BLK | | | SP01086 | | 9 | | ALL |
| E-B | | | | 0-0 | 33-22-41 | L00218 | BLK | | | SP01088 | | 9 | | ALL |
| E-C | | | | 0-0 | 33-22-41 | L00218 | WHT | | | D01766 | | 2 | | ALL |
| E-D | | | | 0-0 | 33-22-41 | L00218 | WHT | | | D01766 | | 3 | | ALL |
| W0115 | 286T0115 | | | E1-3 SHELF, RIGHT SIDE | | | | | | | | | | |
| 034 | 22 | PA | | 3-10 | 34-45-14 | D04879P | | 7 | | TB0105F | A158 | 2 | | 050-099, 150-152 |
| 034 | 22 | PA | | 4-5 | 34-45-14 | D04879P | | 7 | | TB0105F | A158 | 2 | | 153-154 |
| 034 | 22 | PA | | 3-10 | 34-45-14 | D04879P | | 7 | | TB0105G | 158 | 2 | | 155-199, 277-299 |
| 036 | 24 | PK | | 6-4 | 34-45-13 | D04683P | | 41 | | TB0105G | 110 | 2 | | 050-099, 150-199, 277-299 |
| 037 | 22 | PA | | 2-9 | 34-45-14 | D04859P | | 23 | | TB0105G | CAP | Y | | 157, 167-199, 277-299 |
| 039 | 24 | PK | | 8-0 | 34-12-62 | D04683P | | 19 | | TB0105G | 2 | 2 | | ALL |
| 040 | 24 | PK | | 3-2 | 34-31-31 | D05821P | | 16 | | D05615J | 12 | | | ALL |
| 046 | 22 | PA | | 3-8 | 22-14-11 | D04859P | | 1 | | TB0105F | C122 | 2 | | ALL |
| 049 | 24 | PK | | 4-5 | 22-14-21 | D04859P | | 3 | | TB0105H | 112 | 2 | | 050-099 |
| 049 | 24 | PK | | 4-5 | 22-14-21 | D04859P | | 3 | | TB0105H | 19 | 2 | | 150-199, 275-299 |
| 050 | 24 | PK | | 6-0 | 22-14-11 | D04879P | | 6 | | TB0105G | 118 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 10

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0115 | 286T0115 | | | E1-3 SHELF, RIGHT SIDE (continued) | | | | | | | | | | | |
| 051 | 22 | PA | | 3-8 | 22-11-22 | D04859P | | 2 | | | TB0105H | 21 | 2 | | ALL |
| 053 | 24 | PK | | 4-6 | 22-14-11 | D05615J | | 8 | | | TB0105G | 118 | 2 | | ALL |
| 058 | 24 | PK | | 6-3 | 22-14-11 | D04879P | | 1 | | | TB0105G | 116 | 2 | | ALL |
| 063 | 24 | PK | | 4-6 | 22-14-11 | TB0105G | | 116 | 2 | | D05615J | 7 | | | ALL |
| 065 | 24 | PK | | 4-2 | 22-15-12 | D04859P | | 5 | | | TB0105F | C119 | 2 | | ALL |
| 078 | 24 | PK | | 4-2 | 22-15-12 | D04859P | | 16 | | | TB0105F | A119 | 2 | | ALL |
| 188 | 24 | PK | | 4-8 | 34-12-22 | D05821P | | 12 | | | TB0105G | 138 | 2 | | ALL |
| 201B | 24 | PW | IA | 4-10 | 31-31-12 | D05821P | | 3 | | | TB0105F | C129 | 2 | | ALL |
| 201R | 24 | PW | IA | 0-0 | 31-31-12 | D05821P | | 2 | | | TB0105F | A129 | 2 | | ALL |
| 201Z | | | IA | 0-0 | 31-31-12 | D05821P | | 8 | | | GDY0006 | S.. | 2 | | ALL |
| 202B | 24 | PW | IB | 3-0 | 31-31-12 | D05821P | | 18 | | | D05615J | 5 | | | ALL |
| 202R | 24 | PW | IB | 0-0 | 31-31-12 | D05821P | | 17 | | | D05615J | 4 | | | ALL |
| 202Z | | | IB | 0-0 | 31-31-12 | D05821P | | 19 | | | D05615J | 6 | | | ALL |
| 205B | 24 | PW | IE | 3-1 | 34-22-39 | D05615J | | 2 | | | TB0105G | 193 | 2 | | ALL |
| 205R | 24 | PW | IE | 0-0 | 34-22-39 | D05615J | | 1 | | | TB0105G | 192 | 2 | | ALL |
| 205Z | | | IE | 0-0 | 34-22-39 | D05615J | | 3 | | | GDY0016 | S.. | 2 | | ALL |
| 206B | 24 | PW | IF | 3-0 | 73-21-14 | D05613P | | 15 | | | TB0105H | 170 | 2 | | ALL |
| 206R | 24 | PW | IF | 0-0 | 73-21-14 | D05613P | | 14 | | | TB0105H | 168 | 2 | | ALL |
| 206Z | | | IF | 0-0 | 73-21-14 | D05613P | | 16 | | | GDY0011 | S.. | 2 | | ALL |
| 207B | 24 | PW | IG | 3-10 | 22-33-11 | D04683P | | 30 | | | TB0105F | C076 | 2 | | ALL |
| 207R | 24 | PW | IG | 0-0 | 22-33-11 | D04683P | | 29 | | | TB0105F | A076 | 2 | | ALL |
| 207Z | | | IG | 0-0 | 22-33-11 | D04683P | | 28 | | | GDY0012 | S.. | 2 | | ALL |
| 208B | 24 | PW | IH | 3-10 | 22-33-11 | D04683P | | 33 | | | TB0105F | C075 | 2 | | ALL |
| 208R | 24 | PW | IH | 0-0 | 22-33-11 | D04683P | | 32 | | | TB0105F | A075 | 2 | | ALL |
| 208Z | | | IH | 0-0 | 22-33-11 | D04683P | | 31 | | | GDY0011 | S.. | 2 | | 050-099, 277-299 |
| 209B | 24 | PW | II | 3-1 | 77-12-11 | D05613P | | 2 | | | GDY0012 | S.. | 2 | | 150-199, 275-276 |
| 209R | 24 | PW | II | 0-0 | 77-12-11 | D05613P | | 3 | | | TB0105F | C124 | 2 | | 150-157, 275-276 |
| 209Z | | | II | 0-0 | 77-12-11 | D05613P | | 1 | | | TB0105F | A124 | 2 | | 150-157, 275-276 |
| 211 | 20 | UA | | 2-0 | 34-45-14 | TB0105Y | | REF | | IK | GDY0006 | S.. | 2 | | 150-157, 275-276 |
| 211B | 24 | PW | IK | 2-10 | 34-45-14 | D04859P | | 21 | | | GDY0011 | S.. | 2 | | 157, 167-199, 277-299 |
| | | | | | | | | | | | TB0105F | C054 | 2 | | 050-099, 150-156, 162-166 |
| 211B | 24 | PW | IK | 2-7 | 34-45-14 | D04859P | | 21 | | | TB0105Y | C074 | BJ | | 157, 167-199, 277-299 |
| 211R | 24 | PW | IK | 0-0 | 34-45-14 | D04859P | | 20 | | | TB0105F | A054 | 2 | | 050-099, 150-156, 162-166 |
| 211R | 24 | PW | IK | 0-0 | 34-45-14 | D04859P | | 20 | | | TB0105Y | A074 | BJ | | 157, 167-199, 277-299 |
| 211Z | | | IK | 0-0 | 34-45-14 | D04859P | | 22 | | | GDY0009 | S.. | 2 | | 050-099, 150-156, 162-166 |
| 211Z | | | IK | 0-0 | 34-45-14 | D04859P | | 22 | | | TB0105Y | REF | | IK | 157, 167-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0110
Page 11
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0115 | 286T0115 | | | E1-3 SHELF, RIGHT SIDE (continued) | | | | | | | | | | | | |
| 212 | 20 | | UA | 1-6 | 34-45-14 | GDX0010 | S.. | 2 | | TB0105F | REF | | IL | 050-099, 150-156, 162-166 | | |
| 212B | 24 | PW | IL | 3-10 | 34-45-14 | D04683P | | 6 | | TB0105F | C176 | 2 | | 050-099, 150-156, 162-166 | | |
| 212R | 24 | PW | IL | 0-0 | 34-45-14 | D04683P | | 5 | | TB0105F | A176 | 2 | | 050-099, 150-156, 162-166 | | |
| 212Z | | | IL | 0-0 | 34-45-14 | D04683P | | 37 | | TB0105F | REF | | IL | 050-099, 150-156, 162-166 | | |
| 215B | 24 | PW | IO | 6-0 | 34-12-62 | D04683P | | 38 | | TB0105H | 148 | 2 | | 050-099 | | |
| 215B | 24 | PW | IO | 6-0 | 34-12-62 | D04683P | | 16 | | TB0105H | 148 | 2 | | 150-199, 275-299 | | |
| 215R | 24 | PW | IO | 0-0 | 34-12-62 | D04683P | | 39 | | TB0105H | 146 | 2 | | 050-099 | | |
| 215R | 24 | PW | IO | 0-0 | 34-12-62 | D04683P | | 17 | | TB0105H | 146 | 2 | | 150-199, 275-299 | | |
| 215Z | | | IO | 0-0 | 34-12-62 | D04683P | | 40 | | GDY0008 | S.. | 2 | | 050-099 | | |
| 215Z | | | IO | 0-0 | 34-12-62 | D04683P | | 18 | | GDY0008 | S.. | 2 | | 150-199, 275-299 | | |
| 219B | 24 | PW | IS | 8-0 | 31-31-12 | D04683P | | 7 | | TB0105G | 157 | 2 | | ALL | | |
| 219R | 24 | PW | IS | 0-0 | 31-31-12 | D04683P | | 8 | | TB0105G | 156 | 2 | | ALL | | |
| 219Z | | | IS | 0-0 | 31-31-12 | D04683P | | 9 | | GDY0009 | S.. | 2 | | ALL | | |
| 233B | 24 | PW | JH | 3-7 | 22-15-11 | D04859P | | 25 | | TB0105G | 132 | 2 | | ALL | | |
| 233R | 24 | PW | JH | 0-0 | 22-15-11 | D04859P | | 24 | | TB0105G | 133 | 2 | | ALL | | |
| 233Z | | | JH | 0-0 | 22-15-11 | D04859P | | 26 | | GDY0006 | S.. | 2 | | ALL | | |
| 301B | 24 | PM | MA | 4-8 | 34-12-11 | D04859P | | 11 | | TB0105F | C105 | 2 | | ALL | | |
| 301R | 24 | PM | MA | 0-0 | 34-12-11 | D04859P | | 4 | | TB0105F | A105 | 2 | | ALL | | |
| 301Y | 24 | PM | MA | 0-0 | 34-12-11 | D04859P | | 12 | | TB0105F | A106 | 2 | | ALL | | |
| 527B | 24 | PW | VB | 4-0 | 34-22-19 | D05613P | | 12 | | TB0105G | 193 | 2 | | ALL | | |
| 527R | 24 | PW | VB | 0-0 | 34-22-19 | D05613P | | 11 | | TB0105G | 192 | 2 | | ALL | | |
| 527Z | | | VB | 0-0 | 34-22-19 | D05613P | | 13 | | GDY0016 | S.. | 2 | | ALL | | |
| 552B | 24 | PW | WB | 3-10 | 73-21-14 | D05821P | | 5 | | TB0105H | 170 | 2 | | ALL | | |
| 552R | 24 | PW | WB | 0-0 | 73-21-14 | D05821P | | 4 | | TB0105H | 168 | 2 | | ALL | | |
| 552Z | | | WB | 0-0 | 73-21-14 | D05821P | | 6 | | GDY0011 | S.. | 2 | | ALL | | |
| 602 | 24 | PK | | 3-7 | 77-35-11 | D05821P | | 1 | | TB0105F | A077 | 2 | | ALL | | |
| 603 | 24 | PK | | 3-7 | 77-35-11 | D05821P | | 7 | | TB0105F | C077 | 2 | | ALL | | |
| 656B | 24 | PW | F | 3-0 | 22-32-11 | D04683P | | 3 | | TB0105G | 193 | 2 | | ALL | | |
| 656R | 24 | PW | F | 0-0 | 22-32-11 | D04683P | | 2 | | TB0105G | 192 | 2 | | ALL | | |
| 656Z | | | F | 0-0 | 22-32-11 | D04683P | | 4 | | GDY0016 | S.. | 2 | | ALL | | |
| 657B | 24 | PW | G | 3-7 | 22-32-11 | D04683P | | 14 | | TB0105F | C180 | 2 | | ALL | | |
| 657R | 24 | PW | G | 0-0 | 22-32-11 | D04683P | | 13 | | TB0105F | A180 | 2 | | ALL | | |
| 657Z | | | G | 0-0 | 22-32-11 | D04683P | | 15 | | GDY0012 | S.. | 2 | | ALL | | |
| 658B | 24 | PW | H | 3-6 | 22-32-11 | D04683P | | 23 | | TB0105F | C181 | 2 | | ALL | | |
| 658R | 24 | PW | H | 0-0 | 22-32-11 | D04683P | | 22 | | TB0105F | A181 | 2 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 12

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|----------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0115 | 286T0115 | | | E1-3 SHELF, RIGHT SIDE (continued) | | | | | | | | | | | |
| 658Z | | | | H | 0-0 | 22-32-11 | D04683P | 24 | | | GDY0012 | S.. | 2 | | ALL |
| 663B | 24 | PW | | I | 3-2 | 22-32-12 | D04859P | 14 | | | TB0105F | C184 | 2 | | ALL |
| 663R | 24 | PW | | I | 0-0 | 22-32-12 | D04859P | 13 | | | TB0105F | A184 | 2 | | ALL |
| 663Z | | | | I | 0-0 | 22-32-12 | D04859P | 15 | | | GDY0016 | S.. | 2 | | ALL |
| W0117 | 286T0117 | | | E1-4 R TO SHELF | | | | | | | | | | | |
| 002 | 22 | PA | | | 4-0 | 34-22-13 | D05647J | 10 | | | TB0127F | A113 | 2 | | ALL |
| 003 | 24 | PV | AC | | 6-0 | 23-32-21 | D04571P | 5 | | | D01935A | 32 | | | 050-099, 151, 275-299 |
| 003 | 24 | PV | AC | | 6-0 | 23-32-21 | D04571P | 5 | | | D01935B | CAP | Y | | 150, 152-199 |
| 003F | 20 | UA | | | 3-0 | 23-32-21 | D01935A | REF | AC | | GDX0014 | S.. | 2 | | 050-099, 276-299 |
| 003Z | | | | AC | 0-0 | 23-32-21 | D04571P | REF | FC | | D01935A | REF | | AC | 050-099, 151, 275-299 |
| 003Z | | | | AC | 0-0 | 23-32-21 | D04571P | REF | FC | | D01935B | REF | | AC | 150, 152-199 |
| 004 | 20 | UA | | | 5-0 | 23-32-21 | D01935B | REF | AC | | GDX0004 | S.. | 2 | | 150, 152-154 |
| 004 | 20 | UA | | | 5-0 | 23-32-21 | D01935A | REF | AC | | GDX0004 | S.. | 2 | | 151, 275 |
| 004 | 20 | UA | | | 5-0 | 23-32-21 | D01935B | REF | AC | | GDX0014 | S.. | 2 | | 155-199 |
| 005 | 22 | PA | | | 4-2 | 34-22-36 | D05617J | 55 | | | TB0127F | C113 | 2 | | ALL |
| 01CO | | | | A | 0-0 | 23-32-21 | D02257 | =C1 | | | D04571P | =C15 | | | 050-099, 151, 157, 275-299 |
| 01CO | | | | A | 0-0 | 23-32-21 | D02257 | =C1 | | | D04571P | DED | | | 150, 152-156, 162-199 |
| 01CX | | 5X | | A | 6-0 | 23-32-21 | D02257 | =A1 | | | D04571P | 15 | | | ALL |
| 024 | 24 | PK | | | 4-2 | 34-22-37 | D05617J | 29 | | | TB0127F | A155 | 2 | | ALL |
| 029 | 24 | PK | | | 4-2 | 34-22-37 | D05617J | 33 | | | TB0127F | A148 | 2 | | ALL |
| 02CO | | | | B | 0-0 | 23-32-21 | D02259 | =C1 | | | D01935B | =C2 | | | 050-099, 151, 275-299 |
| 02CO | | | | B | 0-0 | 23-32-21 | D02259 | =C1 | | | D01935C | =C2 | | | 150, 152-199 |
| 02CX | | 66 | | B | 1-6 | 23-32-21 | D02259 | =A1 | | | D01935B | A2 | | | 050-099, 151, 275-299 |
| 02CX | | 78 | | B | 1-6 | 23-32-21 | D02259 | =A1 | | | D01935C | A2 | | | 150, 152-199 |
| 030 | 24 | PK | | | 4-2 | 34-22-37 | D05617J | 34 | | | TB0127F | C148 | 2 | | ALL |
| 031 | 24 | PK | | | 4-2 | 34-22-37 | D05617J | 35 | | | TB0127F | A149 | 2 | | ALL |
| 032 | 24 | PK | | | 4-2 | 34-22-37 | D05617J | 36 | | | TB0127F | C149 | 2 | | ALL |
| 044 | 24 | PK | | | 4-2 | 22-15-12 | D05617J | 9 | | | TB0127F | A138 | 2 | | ALL |
| 045 | 24 | PK | | | 5-0 | 22-14-21 | D05617J | 43 | | | TB0127H | 58 | 2 | | ALL |
| 046 | 24 | PK | | | 5-0 | 22-14-21 | D05617J | 44 | | | TB0127H | 62 | 2 | | ALL |
| 047 | 24 | PK | | | 4-0 | 22-14-11 | D05615P | 7 | | | TB0127G | 40 | 2 | | ALL |
| 048 | 24 | PK | | | 4-0 | 22-14-11 | D05615P | 8 | | | TB0127G | 32 | 2 | | ALL |
| 050 | 24 | PK | | | 5-0 | 22-11-22 | D05617J | 41 | | | TB0127G | 45 | 2 | | ALL |
| 051 | 24 | PK | | | 5-0 | 22-11-22 | D05617J | 42 | | | TB0127G | 39 | 2 | | ALL |
| 052 | 24 | PK | | | 4-2 | 22-41-13 | D05617J | 5 | | | TB0127F | C146 | 2 | | ALL |
| 053 | 24 | PK | | | 4-0 | 22-14-21 | D05617J | 45 | | | TB0127G | 32 | 2 | | ALL |
| 054 | 24 | PK | | | 4-0 | 22-14-21 | D05617J | 46 | | | TB0127G | 40 | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0110
Page 13
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0117 | 286T0117 | | | E1-4 R TO SHELF (continued) | | | | | | | | | | | |
| 070 | 22 | | PA | 5-0 | 78-36-21 | D20164B | A10 | | | D07162P | | 1 | | ALL | |
| 071 | 22 | | PA | 5-0 | 78-36-21 | D20164B | K04 | | | D07162P | | 2 | | ALL | |
| 072 | 22 | | PA | 5-0 | 78-36-21 | D20164B | A06 | | | D07162P | | 3 | | ALL | |
| 073 | 22 | | PA | 5-0 | 78-36-21 | D20164B | F14 | | | D07162P | | 4 | | ALL | |
| 074 | 22 | | PA | 5-0 | 78-36-21 | D20164B | A02 | | | D07162P | | 5 | | ALL | |
| 076 | 22 | | PA | 5-0 | 78-36-21 | D20164B | F02 | | | D07162P | | 6 | | ALL | |
| 077 | 22 | | PA | 5-0 | 78-36-21 | D20164B | K08 | | | D07162P | | 7 | | ALL | |
| 078 | 22 | | PA | 5-0 | 78-36-21 | D20164B | K12 | | | D07162P | | 8 | | ALL | |
| 079 | 22 | | PA | 5-0 | 78-36-21 | D20164B | A14 | | | D07162P | | 9 | | ALL | |
| 080 | 22 | | PA | 5-0 | 22-14-31 | D05617J | 30 | | | TB0127F | A163 | 2 | | ALL | |
| 081 | 24 | | PK | 4-2 | 22-15-12 | D05617J | 21 | | | TB0127F | A146 | 2 | | ALL | |
| 082 | 22 | | PA | 3-0 | 78-36-21 | D20164B | F10 | | | GDX0010 | D.. | 2 | | ALL | |
| 083 | 22 | | PA | 3-0 | 78-36-21 | D20164B | F06 | | | GDX0010 | D.. | 2 | | ALL | |
| 101 | 24 | | PK | 3-0 | 34-22-37 | D05617J | 54 | | | TB0127F | A106 | 2 | | ALL | |
| 103 | 24 | | PK | 3-0 | 34-22-36 | D05617J | 53 | | | TB0127G | 105 | 2 | | ALL | |
| 110 | 24 | | PK | 4-0 | 34-31-31 | D05615P | 12 | | | TB0127G | 158 | 2 | | ALL | |
| 201B | 24 | | PW IA | 4-0 | 22-12-21 | D05529P | 10 | | | TB0127G | 162 | 2 | | ALL | |
| 201R | 24 | | PW IA | 0-0 | 22-12-21 | D05529P | 9 | | | TB0127G | 161 | 2 | | ALL | |
| 201Z | | | IA | 0-0 | 22-12-21 | D05529P | 11 | | | GDY0010 | S.. | 2 | | ALL | |
| 202B | 24 | | PW IB | 5-0 | 34-22-38 | D05617J | 51 | | | TB0127F | C054 | 2 | | ALL | |
| 202R | 24 | | PW IB | 0-0 | 34-22-38 | D05617J | 50 | | | TB0127F | A054 | 2 | | ALL | |
| 202Z | | | IB | 0-0 | 34-22-38 | D05617J | 52 | | | GDY0009 | S.. | 2 | | ALL | |
| 203B | 24 | | PW IC | 3-0 | 34-22-39 | D05617J | 7 | | | TB0127F | C102 | 2 | | ALL | |
| 203R | 24 | | PW IC | 0-0 | 34-22-39 | D05617J | 6 | | | TB0127F | A102 | 2 | | ALL | |
| 203Z | | | IC | 0-0 | 34-22-39 | D05617J | 8 | | | GDY0001 | S.. | 2 | | ALL | |
| 204B | 24 | | PW ID | 3-0 | 34-22-39 | D05615P | 2 | | | TB0127Y | C182 | BJ | | ALL | |
| 204R | 24 | | PW ID | 0-0 | 34-22-39 | D05615P | 1 | | | TB0127Y | A182 | BJ | | ALL | |
| 204Z | | | ID | 0-0 | 34-22-39 | D05615P | 3 | | | GDY0012 | S.. | 2 | | 050-099, 152-199, 275-299 | |
| 204Z | | | ID | 0-0 | 34-22-39 | D05615P | 3 | | | GDY0011 | S.. | 2 | | 150-151 | |
| 205B | 24 | | PW IE | 4-0 | 34-22-23 | D05647J | 2 | | | TB0127G | 112 | 2 | | ALL | |
| 205R | 24 | | PW IE | 0-0 | 34-22-23 | D05647J | 1 | | | TB0127G | 111 | 2 | | ALL | |
| 205Z | | | IE | 0-0 | 34-22-23 | D05647J | 3 | | | GDY0001 | S.. | 2 | | ALL | |
| 206B | 24 | | PW IF | 4-0 | 34-22-23 | D05647J | 5 | | | TB0127G | 108 | 2 | | ALL | |
| 206R | 24 | | PW IF | 0-0 | 34-22-23 | D05647J | 4 | | | TB0127G | 107 | 2 | | ALL | |
| 206Z | | | IF | 0-0 | 34-22-23 | D05647J | 6 | | | GDY0001 | S.. | 2 | | ALL | |
| 207B | 24 | | PW IG | 4-0 | 34-22-23 | D05647J | 8 | | | TB0127G | 143 | 2 | | ALL | |
| 207R | 24 | | PW IG | 0-0 | 34-22-23 | D05647J | 7 | | | TB0127G | 142 | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 14

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0117 | 286T0117 | | | E1-4 R TO SHELF (continued) | | | | | | | | | | | | | |
| 207Z | | | | IG | 0-0 | 34-22-23 | D05647J | | 9 | | | | GDY0007 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 207Z | | | | IG | 0-0 | 34-22-23 | D05647J | | 9 | | | | GDY0008 | S.. | 2 | | 150-151 |
| 210B | 24 | PW | IJ | | 5-0 | 34-22-38 | D05617J | | 39 | | | | TB0127X | D065 | BJ | | ALL |
| 210R | 24 | PW | IJ | | 0-0 | 34-22-38 | D05617J | | 38 | | | | TB0127X | C065 | BJ | | ALL |
| 210Z | | | | IJ | 0-0 | 34-22-38 | D05617J | | 40 | | | | GDY0010 | S.. | 2 | | ALL |
| 220B | 24 | PW | IT | | 5-0 | 34-22-34 | D05617J | | 24 | | | | TB0127F | C145 | 2 | | ALL |
| 220R | 24 | PW | IT | | 0-0 | 34-22-34 | D05617J | | 23 | | | | TB0127F | A145 | 2 | | ALL |
| 220Z | | | | IT | 0-0 | 34-22-34 | D05617J | | 25 | | | | GDY0008 | S.. | 2 | | ALL |
| 232B | 24 | PW | JG | | 5-0 | 22-15-11 | D05617J | | 11 | | | | TB0127F | C159 | 2 | | ALL |
| 232R | 24 | PW | JG | | 0-0 | 22-15-11 | D05617J | | 10 | | | | TB0127F | A159 | 2 | | ALL |
| 232Z | | | | JG | 0-0 | 22-15-11 | D05617J | | 12 | | | | GDY0009 | S.. | 2 | | ALL |
| 234B | 24 | PW | JI | | 4-0 | 23-32-21 | D01935B | | 22 | | | | TB0127Y | C181 | BJ | | 050-099, 151, 275-299 |
| 234B | 24 | PW | JI | | 4-0 | 23-32-21 | D01935C | | 22 | | | | TB0127Y | C181 | BJ | | 150, 152-199 |
| 234R | 24 | PW | JI | | 0-0 | 23-32-21 | D01935B | | 21 | | | | TB0127Y | A181 | BJ | | 050-099, 151, 275-299 |
| 234R | 24 | PW | JI | | 0-0 | 23-32-21 | D01935C | | 21 | | | | TB0127Y | A181 | BJ | | 150, 152-199 |
| 234Z | | | | JI | 0-0 | 23-32-21 | D01935B | | DED | | | | GDY0012 | S.. | 2 | | 050-099, 276-299 |
| 234Z | | | | JI | 0-0 | 23-32-21 | D01935C | | | | FI | | GDY0011 | S.. | 2 | | 150, 153-154 |
| 234Z | | | | JI | 0-0 | 23-32-21 | D01935B | | DED | | | | GDY0011 | S.. | 2 | | 151, 275 |
| 234Z | | | | JI | 0-0 | 23-32-21 | D01935C | | | | FI | | GDY0012 | S.. | 2 | | 152, 155-199 |
| 240B | 24 | PW | JO | | 5-0 | 34-22-38 | D05617J | | 48 | | | | TB0127F | C147 | 2 | | ALL |
| 240R | 24 | PW | JO | | 0-0 | 34-22-38 | D05617J | | 47 | | | | TB0127F | A147 | 2 | | ALL |
| 240Z | | | | JO | 0-0 | 34-22-38 | D05617J | | 49 | | | | GDY0008 | S.. | 2 | | ALL |
| 242B | 24 | PW | JQ | | 5-0 | 34-22-38 | D05617J | | 27 | | | | TB0127X | B065 | BJ | | ALL |
| 242R | 24 | PW | JQ | | 0-0 | 34-22-38 | D05617J | | 26 | | | | TB0127X | A065 | BJ | | ALL |
| 242Z | | | | JQ | 0-0 | 34-22-38 | D05617J | | 28 | | | | GDY0010 | S.. | 2 | | ALL |
| 244B | 24 | PW | JS | | 5-0 | 34-22-39 | D05617J | | 14 | | | | TB0127F | C151 | 2 | | ALL |
| 244R | 24 | PW | JS | | 0-0 | 34-22-39 | D05617J | | 13 | | | | TB0127F | A151 | 2 | | ALL |
| 244Z | | | | JS | 0-0 | 34-22-39 | D05617J | | 15 | | | | GDY0008 | S.. | 2 | | 050-099, 150-199, 277-299 |
| 244Z | | | | JS | 0-0 | 34-22-39 | D05617J | | 15 | | | | GDY0009 | S.. | 2 | | 275-276 |
| 245B | 24 | PW | JT | | 5-0 | 34-22-39 | D05617J | | 17 | | | | TB0127F | C152 | 2 | | ALL |
| 245R | 24 | PW | JT | | 0-0 | 34-22-39 | D05617J | | 16 | | | | TB0127F | A152 | 2 | | ALL |
| 245Z | | | | JT | 0-0 | 34-22-39 | D05617J | | 37 | | | | GDY0009 | S.. | 2 | | ALL |
| 247B | 24 | PW | JV | | 4-0 | 23-32-21 | D01935B | | 2 | | | | TB0127Y | C182 | BJ | | 050-099, 151, 275-299 |
| 247B | 22 | PR | JV | | 4-0 | 23-32-21 | D01935C | | 2 | | | | TB0127Y | C182 | BJ | | 150, 152-199 |
| 247R | 24 | PW | JV | | 0-0 | 23-32-21 | D01935B | | 1 | | | | TB0127Y | A182 | BJ | | 050-099, 151, 275-299 |
| 247R | 22 | PR | JV | | 0-0 | 23-32-21 | D01935C | | 1 | | | | TB0127Y | A182 | BJ | | 150, 152-199 |
| 247Z | | | | JV | 0-0 | 23-32-21 | D01935B | | DED | | | | GDY0012 | S.. | 2 | | 050-099, 276-299 |

WIRE LIST
D280T132

91-21-11
Section W0110
Page 15
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0117 | 286T0117 | | | E1-4 R TO SHELF (continued) | | | | | | | | | | | |
| 247Z | | | | JV | 0-0 | 23-32-21 | D01935C | | | | FI | GDY0011 | S.. | 2 | 150, 153-154 |
| 247Z | | | | JV | 0-0 | 23-32-21 | D01935B | | DED | | | GDY0011 | S.. | 2 | 151, 275 |
| 247Z | | | | JV | 0-0 | 23-32-21 | D01935C | | | | FI | GDY0012 | S.. | 2 | 152, 155-199 |
| 257W | 24 | 7K | KG | | 5-0 | 34-43-11 | D05529P | | 1 | | | TB0209R | A006 | 2 | ALL |
| 257WB | 24 | 7K | KG | | 0-0 | 34-43-11 | D05529P | | 2 | | | TB0209R | C006 | 2 | ALL |
| 257Z | | | | KG | 0-0 | 34-43-11 | D05529P | | 3 | | | GDZ0001 | S.. | 2 | ALL |
| 258W | 24 | 7K | KH | | 3-0 | 34-43-21 | D05617J | | 1 | | | TB0209R | A009 | 2 | ALL |
| 258WB | 24 | 7K | KH | | 0-0 | 34-43-21 | D05617J | | 2 | | | TB0209R | C009 | 2 | ALL |
| 258Z | | | | KH | 0-0 | 34-43-21 | D05617J | | 3 | | | TB0209R | | | KH ALL |
| 261B | 24 | PW | KK | | 5-0 | 22-12-21 | D05617J | | 19 | | | TB0127G | 162 | 2 | ALL |
| 261R | 24 | PW | KK | | 0-0 | 22-12-21 | D05617J | | 18 | | | TB0127G | 161 | 2 | ALL |
| 261Z | | | | KK | 0-0 | 22-12-21 | D05617J | | 20 | | | GDY0010 | S.. | 2 | ALL |
| 262B | 24 | PW | KL | | 4-0 | 31-31-12 | D05615P | | 5 | | | TB0127G | 143 | 2 | ALL |
| 262R | 24 | PW | KL | | 0-0 | 31-31-12 | D05615P | | 4 | | | TB0127G | 142 | 2 | ALL |
| 262Z | | | | KL | 0-0 | 31-31-12 | D05615P | | 6 | | | GDY0007 | S.. | 2 | ALL |
| 313 | 20 | UA | | | 3-0 | 23-32-21 | D01935B | | REF | | MM | GDY0014 | S.. | 2 | 050-099, 276-299 |
| 313 | 20 | UA | | | 5-0 | 23-32-21 | D01935A | | REF | | MM | GDY0004 | S.. | 2 | 150, 152-154 |
| 313 | 20 | UA | | | 5-0 | 23-32-21 | D01935B | | REF | | MM | GDY0004 | S.. | 2 | 151, 275 |
| 313 | 20 | UA | | | 3-0 | 23-32-21 | D01935A | | REF | | MM | GDY0014 | S.. | 2 | 155-199 |
| 313B | 24 | PX | MM | | 6-0 | 23-32-21 | D04571P | | 8 | | | D01935B | 18 | | 050-099, 151, 275-299 |
| 313B | 24 | PX | MM | | 6-0 | 23-32-21 | D04571P | | 8 | | | D01935A | CAP | Y | 150, 152-199 |
| 313R | 24 | PX | MM | | 0-0 | 23-32-21 | D04571P | | 9 | | | D01935B | 19 | | 050-099, 151, 275-299 |
| 313R | 24 | PX | MM | | 0-0 | 23-32-21 | D04571P | | 9 | | | D01935A | CAP | Y | 150, 152-199 |
| 313Y | 24 | PX | MM | | 0-0 | 23-32-21 | D04571P | | 10 | | | D01935B | 20 | | 050-099, 151, 275-299 |
| 313Y | 24 | PX | MM | | 0-0 | 23-32-21 | D04571P | | 10 | | | D01935A | CAP | Y | 150, 152-199 |
| 313Z | | | | MM | 0-0 | 23-32-21 | D04571P | | REF | | FC | D01935B | REF | | MM 050-099, 151, 275-299 |
| 313Z | | | | MM | 0-0 | 23-32-21 | D04571P | | REF | | FC | D01935A | REF | | MM 150, 152-199 |
| 527B | 24 | PW | VB | | 6-0 | 23-32-21 | D04571P | | 2 | | | D01935A | 19 | | 050-099, 151 |
| 527B | 24 | PW | VB | | 6-0 | 23-32-21 | D04571P | | 2 | | | D01935B | 18 | | 150, 152-199 |
| 527R | 24 | PW | VB | | 0-0 | 23-32-21 | D04571P | | 1 | | | D01935A | 18 | | 050-099, 151 |
| 527R | 24 | PW | VB | | 0-0 | 23-32-21 | D04571P | | 1 | | | D01935B | 19 | | 150, 152-199 |
| 527Z | | | | VB | 0-0 | 23-32-21 | D04571P | | REF | | FC | D01935A | REF | | VC 050-099, 151 |
| 527Z | | | | VB | 0-0 | 23-32-21 | D04571P | | REF | | FC | D01935B | REF | | VC 150, 152-199 |
| 528 | 20 | UA | | | 3-0 | 23-32-21 | D01935A | | REF | | VC | GDY0014 | S.. | 2 | 050-099, 276-299 |
| 528 | 20 | UA | | | 5-0 | 23-32-21 | D01935B | | REF | | VC | GDY0004 | S.. | 2 | 150, 152-154 |
| 528 | 20 | UA | | | 5-0 | 23-32-21 | D01935A | | REF | | VC | GDY0004 | S.. | 2 | 151, 275 |
| 528 | 20 | UA | | | 3-0 | 23-32-21 | D01935B | | REF | | VC | GDY0014 | S.. | 2 | 155-199 |
| 528B | 24 | PW | VC | | 6-0 | 23-32-21 | D04571P | | 4 | | | D01935A | 21 | | 050-099, 151, 275-299 |
| 528B | 24 | PW | VC | | 6-0 | 23-32-21 | D04571P | | 4 | | | D01935B | 20 | | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 16

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0117 | 286T0117 | | | E1-4 R TO SHELF (continued) | | | | | | | | | | | |
| 528R | 24 | PW | VC | 0-0 | 23-32-21 | D04571P | | 3 | | | D01935A | 20 | | | 050-099, 151, 275-299 |
| 528R | 24 | PW | VC | 0-0 | 23-32-21 | D04571P | | 3 | | | D01935B | 21 | | | 150, 152-199 |
| 528Z | | | VC | 0-0 | 23-32-21 | D04571P | | REF | FC | | D01935A | REF | | VC | 050-099, 151, 275-299 |
| 528Z | | | VC | 0-0 | 23-32-21 | D04571P | | REF | FC | | D01935B | REF | | VC | 150, 152-199 |
| 552 | 20 | UA | | 3-0 | 23-32-21 | D01935B | | REF | WB | | GDX0014 | S.. | 2 | | 050-099, 276-299 |
| 552 | 20 | UA | | 5-0 | 23-32-21 | D01935A | | REF | WB | | STA0330 | CAP | Y | | 150, 152-154 |
| 552 | 20 | UA | | 5-0 | 23-32-21 | D01935B | | REF | WB | | GDX0004 | S.. | 2 | | 151, 275 |
| 552 | 20 | UA | | 3-0 | 23-32-21 | D01935A | | REF | WB | | STA0330 | CAP | Y | | 155-199 |
| 552B | 24 | PW | WB | 6-0 | 23-32-21 | D04571P | | 7 | | | D01935B | 30 | | | 050-099, 151, 275-299 |
| 552B | 24 | PW | WB | 6-0 | 23-32-21 | D04571P | | 7 | | | D01935A | 14 | | | 150, 152-199 |
| 552R | 24 | PW | WB | 0-0 | 23-32-21 | D04571P | | 6 | | | D01935B | 29 | | | 050-099, 151, 275-299 |
| 552R | 24 | PW | WB | 0-0 | 23-32-21 | D04571P | | 6 | | | D01935A | 13 | | | 150, 152-199 |
| 552Z | | | WB | 0-0 | 23-32-21 | D04571P | | REF | FC | | D01935B | REF | | WB | 050-099, 151, 275-299 |
| 552Z | | | WB | 0-0 | 23-32-21 | D04571P | | REF | FC | | D01935A | REF | | WB | 150, 152-199 |
| 553 | 20 | UA | | 3-0 | 23-32-21 | D01935A | | REF | WC | | GDX0014 | S.. | 2 | | 050-099, 276-299 |
| 553 | 20 | UA | | 5-0 | 23-32-21 | D01935B | | REF | WC | | GDX0004 | S.. | 2 | | 150, 152-154 |
| 553 | 20 | UA | | 5-0 | 23-32-21 | D01935A | | REF | WC | | GDX0004 | S.. | 2 | | 151, 275 |
| 553 | 20 | UA | | 3-0 | 23-32-21 | D01935B | | REF | WC | | GDX0014 | S.. | 2 | | 155-199 |
| 553B | 24 | PW | WC | 6-0 | 23-32-21 | D04571P | | 12 | | | D01935A | 14 | | | 050-099, 151, 275-299 |
| 553B | 24 | PW | WC | 6-0 | 23-32-21 | D04571P | | 12 | | | D01935B | 55 | | | 150, 152-199 |
| 553R | 24 | PW | WC | 0-0 | 23-32-21 | D04571P | | 11 | | | D01935A | 12 | | | 050-099, 151, 275-299 |
| 553R | 24 | PW | WC | 0-0 | 23-32-21 | D04571P | | 11 | | | D01935B | 51 | | | 150, 152-199 |
| 553Z | | | WC | 0-0 | 23-32-21 | D04571P | | REF | FC | | D01935A | REF | | WC | 050-099, 151, 275-299 |
| 553Z | | | WC | 0-0 | 23-32-21 | D04571P | | REF | FC | | D01935B | REF | | WC | 150, 152-199 |
| 572B | 24 | PW | WV | 6-0 | 23-32-21 | D04571P | | 2 | | | D01935A | 19 | | | 275-299 |
| 572R | 24 | PW | WV | 0-0 | 23-32-21 | D04571P | | 1 | | | D01935A | 18 | | | 275-299 |
| 572Z | | | WV | 0-0 | 23-32-21 | D04571P | | REF | FC | | D01935A | REF | | VC | 275-299 |
| 616 | 20 | PA | | 3-0 | 23-32-21 | D01935A | | 33 | | | GDX0014 | S.. | 2 | | 050-099, 276-299 |
| 616 | 20 | PA | | 5-0 | 23-32-21 | D01935B | | 33 | | | GDX0004 | S.. | 2 | | 150, 152-154 |
| 616 | 20 | PA | | 5-0 | 23-32-21 | D01935A | | 33 | | | GDX0004 | S.. | 2 | | 151, 275 |
| 616 | 20 | PA | | 3-0 | 23-32-21 | D01935B | | 33 | | | GDX0014 | S.. | 2 | | 155-199 |
| 617 | 20 | PA | | 3-0 | 23-32-21 | D01935A | | 39 | | | GDX0014 | S.. | 2 | | 050-099, 276-299 |
| 617 | 20 | PA | | 5-0 | 23-32-21 | D01935B | | CAP | Y | | GDX0004 | S.. | 2 | | 150, 152-154 |
| 617 | 20 | PA | | 5-0 | 23-32-21 | D01935A | | 39 | | | GDX0004 | S.. | 2 | | 151, 275 |
| 617 | 20 | PA | | 3-0 | 23-32-21 | D01935B | | CAP | Y | | GDX0014 | S.. | 2 | | 155-199 |
| 618 | 20 | PA | | 3-0 | 23-32-21 | D01935A | | 40 | | | GDX0014 | S.. | 2 | | 050-099, 276-299 |
| 618 | 20 | PA | | 5-0 | 23-32-21 | D01935B | | 40 | | | GDX0004 | S.. | 2 | | 150, 152-154 |
| 618 | 20 | PA | | 5-0 | 23-32-21 | D01935A | | 40 | | | GDX0004 | S.. | 2 | | 151, 275 |
| 618 | 20 | PA | | 3-0 | 23-32-21 | D01935B | | 40 | | | GDX0014 | S.. | 2 | | 155-199 |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 17

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|---------|-------------|---|--------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0117 | 286T0117 | | | E1-4 R TO SHELF (continued) | | | | | | | | | | | | | |
| 624 | 20 | | PA | 3-0 | 23-32-21 | D01935B | | 4 | | | | | GDX0014 | D.. | 2 | | 050-099, 276-299 |
| 624 | 20 | | PA | 5-0 | 23-32-21 | D01935C | | 4 | | | | | GDX0004 | S.. | 2 | | 150, 152-154 |
| 624 | 20 | | PA | 5-0 | 23-32-21 | D01935B | | 4 | | | | | GDX0004 | D.. | 2 | | 151, 275 |
| 624 | 20 | | PA | 3-0 | 23-32-21 | D01935C | | 4 | | | | | GDX0014 | S.. | 2 | | 155-199 |
| 625 | 20 | | PA | 6-0 | 23-32-21 | D04571P | | 26 | | | | | D01935B | | 3 | | 050-099, 151, 275-299 |
| 625 | 20 | | PA | 6-0 | 23-32-21 | D04571P | | 26 | | | | | TB0127G | | 83 | 2 | 150, 152-156, 162-199 |
| 625 | 20 | | PA | 6-0 | 23-32-21 | D04571P | | 26 | | | | | SP00008 | | | S | 157 |
| 689 | 20 | | PA | 3-0 | 23-32-21 | D01935A | | 42 | | | | | GDX0014 | S.. | 2 | | 050-099, 276-299 |
| 689 | 20 | | PA | 5-0 | 23-32-21 | D01935B | | 42 | | | | | GDX0004 | S.. | 2 | | 150, 152-154 |
| 689 | 20 | | PA | 5-0 | 23-32-21 | D01935A | | 42 | | | | | GDX0004 | S.. | 2 | | 151, 275 |
| 689 | 20 | | PA | 3-0 | 23-32-21 | D01935B | | 42 | | | | | GDX0014 | S.. | 2 | | 155-199 |
| 690 | 20 | | PA | 3-0 | 23-32-21 | D01935A | | 45 | | | | | GDX0014 | S.. | 2 | | 050-099, 276-299 |
| 690 | 20 | | PA | 5-0 | 23-32-21 | D01935B | | | CAP | Y | | | GDX0004 | S.. | 2 | | 150, 152-154 |
| 690 | 20 | | PA | 5-0 | 23-32-21 | D01935A | | 45 | | | | | GDX0004 | S.. | 2 | | 151, 275 |
| 690 | 20 | | PA | 3-0 | 23-32-21 | D01935B | | | CAP | Y | | | GDX0014 | S.. | 2 | | 155-199 |
| 900 | 20 | | PA | 5-0 | 23-32-21 | D01935C | | | | | | | GDX0004 | S.. | 2 | | 150, 152-154 |
| 900 | 20 | | PA | 5-0 | 23-32-21 | D01935C | | | | | | | GDX0014 | S.. | 2 | | 155-199 |
| 902 | 20 | | PQ | AO | 5-0 | 23-32-21 | D04571P | 14 | | | | | D01935B | | 1 | | 150, 152-199 |
| 902Z | | | | AO | 0-0 | 23-32-21 | D04571P | | | | | | FN | D01935B | DED | | 150, 152-199 |
| 903 | 20 | | PQ | AP | 5-0 | 23-32-21 | D04571P | 16 | | | | | D01935B | | 17 | | 150, 152-199 |
| 903Z | | | | AP | 0-0 | 23-32-21 | D04571P | | | | | | FN | D01935B | DED | | 150, 152-199 |
| 904 | 20 | | PQ | AQ | 5-0 | 23-32-21 | D04571P | 17 | | | | | D01935B | CAP | Y | | 150, 152-199 |
| 904Z | | | | AQ | 0-0 | 23-32-21 | D04571P | | | | | | FQ | D01935B | | | FR 150, 152-199 |
| 905 | 20 | | PQ | AR | 5-0 | 23-32-21 | D04571P | 18 | | | | | D01935B | CAP | Y | | 150, 152-199 |
| 905Z | | | | AR | 0-0 | 23-32-21 | D04571P | | | | | | FQ | D01935B | | | FR 150, 152-199 |
| 906 | 20 | | PQ | AS | 5-0 | 23-32-21 | D04571P | 20 | | | | | D01935B | CAP | Y | | 150, 152-199 |
| 906Z | | | | AS | 0-0 | 23-32-21 | D04571P | | | | | | FQ | D01935B | | | FR 150, 152-199 |
| 907 | 20 | | PQ | AY | 5-0 | 23-32-21 | TB0127G | 84 | 2 | | | | D05637J | | 12 | | 150, 152-156, 162-199 |
| 907 | 20 | | PQ | AY | 5-0 | 23-32-21 | SP00004 | | | S | | | D05637J | | 12 | | 157 |
| 907Z | | | | AY | 0-0 | 23-32-21 | TB0127G | | | | | | FS | D05637J | DED | | 150, 152-156, 162-199 |
| 907Z | | | | AY | 0-0 | 23-32-21 | SP00004 | | | | | | FS | D05637J | | | FU 157 |
| 908B | 22 | | PR | AV | 5-0 | 23-32-21 | D05637J | 9 | | | | | D01935A | | 30 | | 150, 152-199 |
| 908R | 22 | | PR | AV | 0-0 | 23-32-21 | D05637J | 10 | | | | | D01935A | | 29 | | 150, 152-199 |
| 908Z | | | | AV | 0-0 | 23-32-21 | D05637J | 8 | | | | | D01935A | | | | FL 150, 152-156, 162-199 |
| 908Z | | | | AV | 0-0 | 23-32-21 | D05637J | | | | | | FU | D01935A | | | FL 157 |
| 909 | 20 | | PA | | 5-0 | 23-32-21 | D01935A | | | | | | FL | GDX0004 | S.. | 2 | 150, 152-154 |
| 909 | 20 | | PA | | 5-0 | 23-32-21 | D01935A | | | | | | FL | GDX0014 | S.. | 2 | 155-199 |
| 910 | 20 | | PQ | AU | 5-0 | 23-32-21 | TB0127G | 84 | 2 | | | | D01935B | | 45 | | 150, 152-156, 162-199 |
| 910 | 20 | | PQ | AU | 5-0 | 23-32-21 | SP00004 | | | S | | | D01935B | | 45 | | 157 |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 18

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|-------|------|-------|--------|--------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0117 | 286T0117 | | | E1-4 R TO SHELF (continued) | | | | | | | | | | | |
| 910Z | | | | AU | 0-0 | 23-32-21 | TB0127G | | | | FS | | | | FR 150, 152-156, 162-199 |
| 910Z | | | | AU | 0-0 | 23-32-21 | SP00004 | | | | FS | | | | FR 157 |
| 913 | 20 | | PA | | 5-0 | 23-32-21 | SP00006 | | | S | | 24 | | | 157 |
| 916 | 20 | | PA | | 5-0 | 23-32-21 | TB0127G | 83 | 2 | | | 7 | | | 150, 152-156, 162-199 |
| 916 | 20 | | PA | | 5-0 | 23-32-21 | SP00008 | | | S | | 7 | | | 157 |
| 917 | 20 | | PA | | 5-0 | 23-32-21 | TB0127G | 83 | 2 | | | 3 | | | 150, 152-156, 162-199 |
| 917 | 20 | | PA | | 5-0 | 23-32-21 | SP00008 | | | S | | 3 | | | 157 |
| 918 | 20 | | PQ | AX | 5-0 | 23-32-21 | TB0127G | 84 | 2 | | | 19 | | | 150, 152-156, 162-199 |
| 918 | 20 | | PQ | AX | 5-0 | 23-32-21 | SP00004 | | | S | | 19 | | | 157 |
| 918Z | | | | AX | 0-0 | 23-32-21 | TB0127G | | | | FS | | | | FL 150, 152-156, 162-199 |
| 918Z | | | | AX | 0-0 | 23-32-21 | SP00004 | | | | FS | | | | FL 157 |
| 920 | 20 | | PA | | 3-0 | 23-32-21 | D01935A | | | | FL | | S | | 150, 152-199 |
| 921 | 20 | | PA | | 3-0 | 23-32-21 | D01935B | | | | FR | | S | | 150, 152-199 |
| 924B | 22 | | PR | AB | 5-0 | 23-32-21 | D04571P | 24 | | | | 38 | | | 150, 152-199 |
| 924R | 22 | | PR | AB | 0-0 | 23-32-21 | D04571P | 23 | | | | 37 | | | 150, 152-199 |
| 924Z | | | | AB | 0-0 | 23-32-21 | D04571P | | | | FT | | DED | | 150, 152-199 |
| 925B | 22 | | PR | AT | 5-0 | 23-32-21 | D04571P | 28 | | | | 44 | | | 150, 152-199 |
| 925R | 22 | | PR | AT | 0-0 | 23-32-21 | D04571P | 27 | | | | 43 | | | 150, 152-199 |
| 925Z | | | | AT | 0-0 | 23-32-21 | D04571P | | | | FT | | | FD | 150, 152-199 |
| 926 | 22 | | PA | | 5-0 | 23-32-21 | D01935B | | | | FD | | S.. 2 | | 150, 152-154 |
| 926 | 22 | | PA | | 5-0 | 23-32-21 | D01935B | | | | FD | | S.. 2 | | 155-199 |
| FRB | | | | | 0-3 | 34-43-21 | TB0209R | | | | KH | | S.. 2 | | ALL |
| FRC | | | | | 0-0 | 23-32-21 | D04571P | 25 | | | | | REF | FC | ALL |
| FRN | | | | | 0-0 | 23-32-21 | D04571P | | | | FN | | 13 | | 150, 152-199 |
| FRQ | | | | | 0-0 | 23-32-21 | D04571P | | | | FQ | | 21 | | 150, 152-199 |
| FRT | | | | | 0-0 | 23-32-21 | D04571P | | | | FT | | 22 | | 150, 152-199 |
| FRU | | | | | 0-0 | 23-32-21 | D05637J | | | | FU | | 8 | | 157 |
| W0119 | 286T0119 | | | E1-5 SHELF R | | | | | | | | | | | |
| 001 | 22 | | PQ | AA | 2-8 | 22-11-22 | D00381C | | 1 | | | | | | ALL |
| 001Z | | | | AA | 0-0 | 22-11-22 | D00381C | | DED | | | | | | ALL |
| 002 | 20 | | PQ | AB | 2-8 | 22-11-22 | D00381C | | 2 | | | | | | ALL |
| 002Z | | | | AB | 0-0 | 22-11-22 | D00381C | | DED | | | | | | ALL |
| 003 | 22 | | PA | | 4-4 | 22-11-22 | D04247P | | 14 | | | | | | ALL |
| 004 | 20 | | PA | | 2-0 | 22-11-21 | D00381C | | 4 | | | | A.. 2 | | ALL |
| 005 | 22 | | PQ | AE | 2-8 | 22-11-22 | D00381C | | 5 | | | | 130 2 | | ALL |
| 005Z | | | | AE | 0-0 | 22-11-22 | D00381C | | DED | | | | DED | | ALL |
| 006 | 22 | | PA | | 4-3 | 22-11-21 | D00381C | | 6 | | | | 13 | | ALL |
| 007 | 20 | | PA | | 2-0 | 22-11-21 | D00381C | | 7 | | | | D.. 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0110
Page 19
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|----------|-------|---------|-------|------|------|---------|-------|------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | |
| 008 | 22 | PQ | AH | 4-4 | 22-11-22 | | D04247P | | 1 | | TB0119H | 130 | 2 | | ALL |
| 008Z | | | AH | 0-0 | 22-11-22 | | D04247P | | DED | | TB0119H | DED | | | ALL |
| 009 | 20 | PA | | 3-3 | 22-11-22 | | D00381C | | 9 | | TB0119F | A155 | 2 | | ALL |
| 010 | 22 | PA | | 4-2 | 22-11-22 | | D04595P | | 3 | | TB0119G | 27 | 2 | | ALL |
| 011 | 22 | PA | | 4-0 | 22-11-22 | | D04595P | | 1 | | TB0119H | 32 | 2 | | ALL |
| 012 | 22 | PA | | 3-0 | 22-11-22 | | D00381A | | H15 | | TB0119G | 27 | 2 | | ALL |
| 013 | 22 | PA | | 2-11 | 22-11-22 | | D00381B | | H15 | | TB0119G | 27 | 2 | | ALL |
| 014 | 22 | PQ | AN | 3-11 | 22-11-22 | | D04595P | | 2 | | TB0119H | 130 | 2 | | ALL |
| 014Z | | | AN | 0-0 | 22-11-22 | | D04595P | | DED | | TB0119H | DED | | | ALL |
| 015 | 22 | PA | | 3-9 | 22-11-22 | | D00381B | | F15 | | D04369P | 3 | | | ALL |
| 017 | 24 | PK | | 1-6 | 22-11-22 | | D00381A | | B13 | | D00381A | B14 | | | ALL |
| 018 | 22 | PA | | 3-6 | 22-11-22 | | D00381B | | H11 | | D04857P | 2 | | | ALL |
| 019 | 20 | PA | | 3-2 | 22-11-22 | | D04369P | | 4 | | GDX0005 | D.. | 2 | | 050-099, 150-199, 275-278 |
| 019 | 20 | PA | | 5-0 | 22-11-22 | | D04369P | | 4 | | GDX0005 | D.. | 2 | | 280-299 |
| 020 | 24 | PK | | 1-6 | 22-11-22 | | D00381B | | A03 | | D00381B | E04 | | | ALL |
| 021 | 24 | PK | | 3-0 | 22-11-22 | | D00381B | | A06 | | D05617P | 41 | | | ALL |
| 022 | 24 | PK | | 3-0 | 22-11-22 | | D00381B | | C07 | | D05617P | 42 | | | ALL |
| 023 | 22 | PA | | 4-9 | 22-11-22 | | D00381B | | C15 | | D04529P | 11 | | | ALL |
| 024 | 22 | PA | | 4-10 | 22-11-22 | | D00381A | | C15 | | D04529P | 14 | | | ALL |
| 025 | 22 | PA | | 4-10 | 22-11-22 | | D00381B | | A15 | | D04385P | 1 | | | ALL |
| 026 | 22 | PA | | 4-10 | 22-11-22 | | D00381A | | A15 | | D04385P | 25 | | | ALL |
| 027 | 22 | PA | | 2-0 | 22-11-22 | | D00381A | | A04 | | GDX0005 | D.. | 2 | | ALL |
| 028 | 22 | PA | | 2-0 | 22-11-22 | | D00381A | | G11 | | GDX0005 | D.. | 2 | | ALL |
| 029 | 24 | PK | | 4-9 | 33-16-14 | | D04793P | | 16 | | TB0119F | C112 | 2 | | ALL |
| 030 | 22 | PA | | 4-7 | 22-11-22 | | D00381B | | K15 | | D04385P | 28 | | | ALL |
| 031 | 22 | PA | | 4-10 | 22-11-22 | | D00381A | | K15 | | D04385P | 49 | | | ALL |
| 032 | 22 | PA | | 3-9 | 22-12-21 | | D00381A | | F15 | | D04369P | 2 | | | ALL |
| 033 | 22 | PA | | 3-9 | 22-12-21 | | D00381B | | E09 | | D04369P | 1 | | | ALL |
| 034 | 24 | PK | | 3-9 | 22-12-21 | | D00381B | | E10 | | D04857P | 45 | | | ALL |
| 035 | 24 | PK | | 5-3 | 22-12-21 | | D00381B | | D08 | | D04883P | 6 | | | ALL |
| 036 | 24 | PK | | 5-3 | 22-12-21 | | D00381B | | C09 | | D04883P | 7 | | | ALL |
| 037 | 24 | PK | | 5-3 | 22-12-21 | | D00381B | | D10 | | D04883P | 8 | | | ALL |
| 038 | 24 | PK | | 5-3 | 22-12-21 | | D00381B | | D09 | | D04883P | 9 | | | ALL |
| 042 | 20 | PA | | 4-7 | 22-12-21 | | D04369P | | 16 | | GDX0011 | S.. | 2 | | ALL |
| 043 | 12 | PA | | 6-0 | 34-21-21 | | D05680P | | 2 | | D05619J | 14 | | | ALL |
| 045 | 24 | PK | | 3-7 | 22-13-21 | | D00381B | | H03 | | TB0119G | 76 | 2 | | ALL |
| 046 | 24 | PK | | 3-11 | 22-14-21 | | D04393P | | 14 | | TB0119H | 51 | 2 | | ALL |
| 048 | 24 | PK | | 3-0 | 22-14-21 | | D00381B | | K10 | | TB0119H | 51 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 20

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|---|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | |
| 049 | 24 | | PK | | 3-3 | 22-14-21 | D00381B | | K11 | | TB0119H | 57 | 2 | | ALL |
| 050 | 24 | | PK | | 3-1 | 22-14-21 | D00381B | | K03 | | TB0119H | 49 | 2 | | ALL |
| 051 | 24 | | PK | | 3-2 | 22-14-21 | D00381B | | K12 | | D05617P | 44 | | | ALL |
| 052 | 22 | | PA | | 4-3 | 22-14-21 | D04393P | | 17 | | TB0119H | 32 | 2 | | ALL |
| 053 | 24 | | PK | | 3-9 | 22-14-21 | D00381B | | E12 | | D04857P | 3 | | | ALL |
| 054 | 24 | | PK | | 3-6 | 22-14-21 | D04393P | | 15 | | TB0119H | 57 | 2 | | ALL |
| 055 | 24 | | PK | | 2-10 | 22-14-21 | D00381A | | E12 | | TB0119F | C126 | 2 | | ALL |
| 056 | 22 | | PA | | 2-10 | 22-14-21 | D00381A | | F01 | | TB0119F | A126 | 2 | | ALL |
| 057 | 24 | | PK | | 2-9 | 22-14-21 | D00381B | | J11 | | TB0119H | 148 | 2 | | ALL |
| 058 | 24 | | PK | | 1-6 | 22-11-22 | D00381B | | F04 | | D00381B | C13 | | | 150-199, 277-299 |
| 059 | 24 | | PK | | 3-0 | 22-14-21 | D00381B | | J12 | | D05617P | 43 | | | ALL |
| 060 | 22 | | PA | | 2-8 | 22-14-21 | D00381A | | C13 | | TB0119G | 39 | 2 | | ALL |
| 061 | 24 | | PK | | 1-6 | 22-11-22 | D00381B | | K13 | | D00381B | K14 | | | ALL |
| 062 | 24 | | PK | | 3-0 | 22-14-21 | D00381B | | G12 | | D05617P | 45 | | | ALL |
| 063 | 24 | | PK | | 3-0 | 22-14-21 | D00381B | | K02 | | D05617P | 46 | | | ALL |
| 064 | 24 | | PV | CN | 2-10 | 22-14-21 | D00381A | | G12 | | TB0119F | A127 | 2 | | ALL |
| 064Z | | | | CN | 0-0 | 22-14-21 | D00381A | | DED | | TB0119F | DED | | | ALL |
| 068 | 24 | | PK | | 3-7 | 22-14-21 | D04393P | | 13 | | TB0119H | 148 | 2 | | ALL |
| 069 | 22 | | PA | | 3-8 | 22-14-11 | D04857P | | 1 | | TB0119G | 39 | 2 | | ALL |
| 071 | 24 | | PK | | 4-0 | 31-51-11 | D04247P | | 2 | | D04325P | 14 | | | 050-099, 150-199, 275-278 280-299 |
| 071 | 24 | | PK | | 4-2 | 31-51-11 | D04247P | | 2 | | D04325P | 14 | | | ALL |
| 072 | 22 | | PA | | 5-2 | 34-22-26 | D04247P | | 9 | | TB0119F | A111 | 2 | | ALL |
| 073 | 22 | | PA | | 4-4 | 34-22-26 | D04393P | | 16 | | TB0119G | 125 | 2 | | ALL |
| 074 | 22 | | PA | | 4-10 | 22-14-31 | D04793P | | 1 | | TB0119G | 39 | 2 | | ALL |
| 075 | 22 | | PA | | 3-1 | 22-14-31 | D05617P | | 30 | | TB0119G | 39 | 2 | | ALL |
| 076 | 22 | | PA | | 3-2 | 22-14-31 | D04793P | | 2 | | D04873P | 2 | | | ALL |
| 077 | 24 | | PV | DB | 2-10 | 22-15-12 | D00381A | | E03 | | TB0119F | C127 | 2 | | ALL |
| 077Z | | | | DB | 0-0 | 22-15-12 | D00381A | | DED | | TB0119F | DED | | | ALL |
| 079 | 24 | | PK | | 4-7 | 22-41-13 | D04393P | | 36 | | D05617P | 5 | | | ALL |
| 080 | 24 | | PK | | 3-10 | 22-41-13 | D04393P | | 35 | | D00381B | F10 | | | ALL |
| 081 | 24 | | PK | | 3-10 | 22-41-13 | D04393P | | 37 | | D00381B | F09 | | | ALL |
| 083 | 24 | | PK | | 2-9 | 22-15-12 | D00381A | | K01 | | TB0119F | A123 | 2 | | ALL |
| 084 | 24 | | PK | | 3-3 | 22-15-12 | D04857P | | 16 | | TB0119G | 53 | 2 | | ALL |
| 085 | 24 | | PK | | 3-3 | 22-15-12 | D00381A | | G10 | | TB0119G | 53 | 2 | | ALL |
| 086 | 24 | | PK | | 3-11 | 22-15-12 | D05617P | | 21 | | TB0119G | 53 | 2 | | ALL |
| 087 | 24 | | PK | | 3-0 | 22-15-12 | D00381A | | K03 | | TB0119F | A150 | 2 | | ALL |
| 088 | 24 | | PK | | 5-2 | 22-12-21 | D04361P | | 5 | | D00381A | F12 | | | ALL |
| 089 | 24 | | PK | | 2-8 | 22-12-21 | D00381B | | G09 | | TB0119G | 47 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0110
Page 21
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | | | |
| 090 | 24 | | PK | | 2-8 | 22-12-21 | D00381A | G09 | | | | | TB0119G | 47 | 2 | | ALL |
| 091 | 22 | | PA | | 4-11 | 22-22-21 | D04361P | | 10 | | | | TB0119G | 47 | 2 | | ALL |
| 092 | 24 | | PK | | 3-9 | 22-41-11 | D00381B | | C06 | | | | D04793P | 12 | | | ALL |
| 093 | 24 | | PV | DR | 2-10 | 22-41-11 | D00381A | | A03 | | | | TB0119F | A128 | 2 | | ALL |
| 093Z | | | | DR | 0-0 | 22-41-11 | D00381A | | DED | | | | TB0119F | DED | | | ALL |
| 094 | 24 | | PV | DS | 2-10 | 22-15-12 | D00381A | | G01 | | | | TB0119F | C128 | 2 | | ALL |
| 094Z | | | | DS | 0-0 | 22-15-12 | D00381A | | DED | | | | TB0119F | DED | | | ALL |
| 095 | 24 | | PK | | 2-8 | 22-13-21 | D00381B | | H02 | | | | TB0119G | 142 | 2 | | ALL |
| 096 | 22 | | PA | | 4-5 | 34-22-26 | D04805P | | 55 | | | | TB0119G | 142 | 2 | | ALL |
| 101 | 20 | | PA | | 3-4 | 34-31-21 | D04247P | | 11 | | | | D00377C | 2 | | | ALL |
| 102 | 20 | | PA | | 2-0 | 34-31-21 | GDX0011 | | A.. | 2 | | | D00377C | 3 | | | ALL |
| 103 | 20 | | PA | | 2-0 | 34-31-21 | GDX0011 | | D.. | 2 | | | D00377C | 4 | | | ALL |
| 104 | 24 | | PK | | 1-6 | 34-31-21 | D00377B | | B03 | | | | D00377B | C03 | | | ALL |
| 105 | 24 | | PK | | 1-6 | 34-31-21 | D00377B | | B05 | | | | D00377B | C05 | | | ALL |
| 107 | 22 | | PA | | 5-0 | 34-31-21 | D04369P | | 5 | | | | TB0119G | 76 | 2 | | ALL |
| 108 | 22 | | PA | | 3-4 | 34-31-21 | D00377B | | D15 | | | | TB0119G | 56 | 2 | | ALL |
| 109 | 22 | | PA | | 3-7 | 34-31-21 | D04369P | | 11 | | | | TB0119F | A021 | 2 | | ALL |
| 110 | 24 | | PK | | 3-2 | 34-33-21 | D04857P | | 41 | | | | TB0119G | 56 | 2 | | ALL |
| 111 | 22 | | PA | | 4-2 | 34-31-21 | D04805P | | 1 | | | | TB0119G | 56 | 2 | | ALL |
| 112 | 24 | | PK | | 3-0 | 22-13-21 | D00377B | | C01 | | | | TB0119G | 76 | 2 | | ALL |
| 120 | 24 | | PK | | 2-9 | 22-15-12 | D00381A | | F09 | | | | TB0119G | 40 | 2 | | ALL |
| 123 | 24 | | PK | | 5-0 | 34-22-27 | D04393P | | 31 | | | | TB0119G | 105 | 2 | | ALL |
| 125 | 24 | | PK | | 3-8 | 22-15-12 | D04857P | | 44 | | | | TB0119G | 40 | 2 | | ALL |
| 126 | 24 | | PK | | 3-4 | 22-15-12 | D05617P | | 9 | | | | TB0119G | 40 | 2 | | ALL |
| 129 | 24 | | PK | | 6-0 | 31-51-41 | D04369P | | 21 | | | | D04325P | 21 | | | ALL |
| 130 | 24 | | PK | | 4-0 | 34-22-27 | D04393P | | 44 | | | | TB0119G | 138 | 2 | | ALL |
| 131 | 24 | | PK | | 3-3 | 34-22-37 | D05617P | | 54 | | | | TB0119G | 138 | 2 | | ALL |
| 139 | 24 | | PK | | 1-6 | 22-11-22 | D00381B | | D03 | | | | D00381B | K04 | | | ALL |
| 143 | 20 | | PA | | 3-1 | 27-48-11 | D04385P | | 4 | | | | GDX0011 | A.. | 2 | | 157, 167-199, 277-299 |
| 144 | 24 | | PK | | 1-6 | 22-11-22 | D00381B | | K09 | | | | D00381B | F11 | | | 050-099, 150-199, 277-299 |
| 155 | 20 | | PQ | GE | 5-3 | 27-32-21 | D04247P | | 12 | | | | D04345P | 3 | | | ALL |
| 155Z | | | | GE | 0-0 | 27-32-21 | D04247P | | DED | | | | D04345P | DED | | | ALL |
| 156 | 20 | | PA | | 5-3 | 27-32-21 | D04325P | | 13 | | | | D04345P | 4 | | | ALL |
| 159 | 22 | | PA | | 3-11 | 27-61-11 | D04361P | | 16 | | | | D04883P | 17 | | | ALL |
| 160 | 24 | | PK | | 3-3 | 34-22-36 | D05617P | | 53 | | | | TB0119H | 139 | 2 | | ALL |
| 161 | 20 | | PA | | 6-9 | 27-41-21 | D04369P | | 13 | | | | D04385P | 33 | | | ALL |
| 162 | 20 | | PA | | 6-9 | 27-41-21 | D04369P | | 14 | | | | D04385P | 34 | | | ALL |
| 165Y | 22 | | PJ | | 6-5 | 27-41-21 | D04345P | | 1 | | | | D04385P | 37 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 22

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | | |
| 167Y | 22 | | PJ | 3-0 | 27-41-21 | D04361P | | 3 | | | D04385P | | 35 | | 050-099, 150-154, 163-165, 275-276 | |
| 167Y | 22 | | PJ | 3-6 | 27-41-21 | D04361P | | 3 | | | D04385P | | 35 | | 155-162, 166-199, 277-299 | |
| 168Y | 22 | | PJ | 6-4 | 27-41-21 | D04345P | | 2 | | | D04385P | | 36 | | 050-099 | |
| 170 | 24 | | PK | 3-4 | 27-48-11 | D04247P | | 24 | | | TB0119G | | 69 | 2 | ALL | |
| 171 | 24 | | PK | 4-9 | 27-48-11 | D04369P | | 15 | | | TB0119G | | 69 | 2 | ALL | |
| 172 | 24 | | PK | 3-9 | 27-48-11 | D04385P | | 41 | | | TB0119G | | 69 | 2 | ALL | |
| 173 | 24 | | PK | 6-9 | 27-48-11 | D04369P | | 22 | | | D04385P | | 42 | | ALL | |
| 174 | 24 | | PK | 6-9 | 27-48-11 | D04369P | | 23 | | | D04385P | | 43 | | ALL | |
| 175 | 24 | | PK | 6-9 | 31-51-42 | D04325P | | 12 | | | D04369P | | 10 | | 050-099, 150-199, 275-278 | |
| 175 | 24 | | PK | 6-0 | 31-51-42 | D04325P | | 12 | | | D04369P | | 10 | | 280-299 | |
| 176 | 24 | | PK | 4-0 | 31-51-41 | D04325P | | 7 | | | D04793P | | 4 | | 050-099, 150-199, 275-278 | |
| 176 | 24 | | PK | 4-2 | 31-51-41 | D04325P | | 7 | | | D04793P | | 4 | | 280-299 | |
| 179 | 24 | | PK | 4-5 | 34-22-27 | D04393P | | 4 | | | TB0119G | | 22 | 2 | ALL | |
| 180 | 24 | | PK | 4-5 | 34-22-27 | D04393P | | 5 | | | TB0119G | | 23 | 2 | ALL | |
| 181 | 24 | | PK | 4-5 | 34-22-27 | D04393P | | 6 | | | TB0119H | | 24 | 2 | ALL | |
| 183 | 24 | | PK | 4-5 | 34-22-27 | D04393P | | 11 | | | TB0119G | | 26 | 2 | ALL | |
| 185 | 22 | | PA | 3-11 | 22-24-21 | D04883P | | 1 | | | D04361P | | 14 | | ALL | |
| 186 | 24 | | PK | 4-0 | 27-32-21 | D04793P | | 6 | | | D04325P | | 6 | | 050-099, 150-199, 275-278 | |
| 186 | 24 | | PK | 3-8 | 27-32-21 | D04793P | | 6 | | | D04325P | | 6 | | 280-299 | |
| 187 | 24 | | PK | 4-3 | 34-22-37 | D05617P | | 29 | | | D04393P | | 30 | | ALL | |
| 188 | 24 | | PK | 3-9 | 34-43-21 | D04849P | | 1 | | | TB0119H | | 24 | 2 | ALL | |
| 189 | 24 | | PK | 3-4 | 34-22-26 | D04247P | | 25 | | | TB0119F | A071 | 2 | | ALL | |
| 190 | 24 | | PK | 2-11 | 34-22-37 | D05617P | | 33 | | | TB0119G | | 22 | 2 | ALL | |
| 191 | 24 | | PK | 3-1 | 34-22-37 | D05617P | | 34 | | | TB0119G | | 26 | 2 | ALL | |
| 192 | 24 | | PK | 2-11 | 34-22-37 | D05617P | | 35 | | | TB0119G | | 23 | 2 | ALL | |
| 193 | 24 | | PK | 2-11 | 34-22-37 | D05617P | | 36 | | | TB0119H | | 24 | 2 | ALL | |
| 196 | 24 | | PK | 3-0 | 31-31-19 | TB0119G | | 105 | 2 | | TB0119D | C104 | 2 | | ALL | |
| 197 | 24 | | PK | 2-11 | 31-31-19 | TB0119H | | 24 | 2 | | TB0119D | C036 | 2 | | ALL | |
| 198 | 24 | | PK | 6-10 | 31-31-19 | D04447P | | 6 | | | TB0119D | A104 | 2 | | ALL | |
| 199 | 24 | | PK | 6-0 | 31-31-19 | D04447P | | 7 | | | TB0119D | A036 | 2 | | ALL | |
| 204B | 20 | | PB | ID | 2-9 | 22-11-21 | D00381C | 11 | | | TB0119H | | 45 | 2 | ALL | |
| 204R | 20 | | PB | ID | 0-0 | 22-11-21 | D00381C | 10 | | | TB0119H | | 43 | 2 | ALL | |
| 205B | 22 | | PB | IE | 4-7 | 22-11-21 | D04529P | 2 | | | TB0119H | | 45 | 2 | ALL | |
| 205R | 22 | | PB | IE | 0-0 | 22-11-21 | D04529P | 1 | | | TB0119H | | 43 | 2 | ALL | |

WIRE LIST

D280T132

91-21-11
Section W0110
Page 23
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | | | |
| 206B | 22 | | PB | IF | 4-9 | 22-11-21 | D04385P | | 6 | | | | TB0119H | 45 | 2 | | ALL |
| 206R | 22 | | PB | IF | 0-0 | 22-11-21 | D04385P | | 5 | | | | TB0119H | 43 | 2 | | ALL |
| 207B | 22 | | PB | IG | 4-9 | 22-11-21 | D04385P | | 8 | | | | TB0119H | 45 | 2 | | ALL |
| 207R | 22 | | PB | IG | 0-0 | 22-11-21 | D04385P | | 7 | | | | TB0119H | 43 | 2 | | ALL |
| 208B | 24 | | PW | IH | 2-8 | 22-12-21 | D00381B | | B04 | | | | TB0119G | 35 | 2 | | ALL |
| 208R | 24 | | PW | IH | 0-0 | 22-12-21 | D00381B | | B03 | | | | TB0119G | 34 | 2 | | ALL |
| 208Z | | | | IH | 0-0 | 22-12-21 | D00381B | | DED | | | | GDY0006 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 208Z | | | | IH | 0-0 | 22-12-21 | D00381B | | DED | | | | GDY0007 | S.. | 2 | | 150-151 |
| 209B | 24 | | PL | II | 5-4 | 27-58-21 | D04883P | | 25 | | | | D04385P | 44 | | | ALL |
| 209R | 24 | | PL | II | 0-0 | 27-58-21 | D04883P | | 26 | | | | D04385P | 45 | | | ALL |
| 210B | 24 | | PL | IJ | 4-1 | 27-32-21 | D04883P | | 23 | | | | D04873P | 19 | | | ALL |
| 210R | 24 | | PL | IJ | 0-0 | 27-32-21 | D04883P | | 22 | | | | D04873P | 18 | | | ALL |
| 211B | 22 | | PB | IK | 4-10 | 22-12-21 | D00381B | | D11 | | | | D04385P | 10 | | | ALL |
| 211R | 22 | | PB | IK | 0-0 | 22-12-21 | D00381B | | E11 | | | | D04385P | 9 | | | ALL |
| 212 | 20 | | UA | | 1-6 | 22-12-21 | GDY0005 | | S.. | 2 | | | D00381B | | | FA | ALL |
| 212B | 24 | | PW | IL | 3-9 | 22-12-21 | D00381B | | C02 | | | | D04857P | 47 | | | ALL |
| 212R | 24 | | PW | IL | 0-0 | 22-12-21 | D00381B | | C01 | | | | D04857P | 46 | | | ALL |
| 212Z | | | | IL | 0-0 | 22-12-21 | D00381B | | | | FA | | D04857P | 48 | | | ALL |
| 213 | 20 | | UA | | 1-6 | 34-61-26 | GDY0005 | | S.. | 2 | | | D00381A | | | FB | 050-099, 275-299 |
| 213 | 20 | | UA | | 1-6 | 34-61-26 | GDY0005 | | S.. | 2 | | | D00381A | | | IM | 150-199 |
| 213B | 24 | | PW | IM | 4-7 | 34-61-26 | D00381A | | D09 | | | | D04805P | 15 | | | ALL |
| 213R | 24 | | PW | IM | 0-0 | 34-61-26 | D00381A | | C09 | | | | D04805P | 14 | | | ALL |
| 213Z | | | | IM | 0-0 | 34-61-26 | D00381A | | | | FB | | D04805P | 16 | | | 050-099, 275-299 |
| 213Z | | | | IM | 0-0 | 34-61-26 | D00381A | | | | IM | | D04805P | 16 | | | 150-199 |
| 214B | 24 | | PW | IN | 4-0 | 22-12-21 | D04595P | | 5 | | | | TB0119G | 35 | 2 | | ALL |
| 214R | 24 | | PW | IN | 0-0 | 22-12-21 | D04595P | | 4 | | | | TB0119G | 34 | 2 | | ALL |
| 214Z | | | | IN | 0-0 | 22-12-21 | D04595P | | 6 | | | | GDY0006 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 214Z | | | | IN | 0-0 | 22-12-21 | D04595P | | 6 | | | | GDY0007 | S.. | 2 | | 150-151 |
| 215B | 24 | | PW | IO | 3-4 | 22-12-21 | D00381A | | B10 | | | | TB0119H | 67 | 2 | | ALL |
| 215R | 24 | | PW | IO | 0-0 | 22-12-21 | D00381A | | A10 | | | | TB0119H | 65 | 2 | | ALL |
| 215Z | | | | IO | 0-0 | 22-12-21 | D00381A | | DED | | | | GDY0010 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 215Z | | | | IO | 0-0 | 22-12-21 | D00381A | | DED | | | | GDY0011 | S.. | 2 | | 150-151 |
| 216B | 24 | | PW | IP | 3-4 | 22-12-21 | D05617P | | 19 | | | | TB0119G | 42 | 2 | | ALL |
| 216R | 24 | | PW | IP | 0-0 | 22-12-21 | D05617P | | 18 | | | | TB0119G | 41 | 2 | | ALL |
| 216Z | | | | IP | 0-0 | 22-12-21 | D05617P | | 20 | | | | GDY0007 | S.. | 2 | | ALL |
| 218B | 24 | | PW | IR | 2-9 | 22-12-21 | D00381B | | B02 | | | | TB0119G | 42 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 24

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | |
| 218R | 24 | PW | IR | | 0-0 | 22-12-21 | D00381B | B01 | | | TB0119G | 41 | 2 | | ALL |
| 218Z | | | IR | | 0-0 | 22-12-21 | D00381B | DED | | | GDY0007 | S.. | 2 | | ALL |
| 221B | 24 | PW | IU | | 3-9 | 22-13-21 | D04595P | 8 | | | TB0119G | 38 | 2 | | ALL |
| 221R | 24 | PW | IU | | 0-0 | 22-13-21 | D04595P | 7 | | | TB0119G | 37 | 2 | | ALL |
| 221Z | | | IU | | 0-0 | 22-13-21 | D04595P | 9 | | | GDY0007 | S.. | 2 | | ALL |
| 223B | 24 | PW | IW | | 2-8 | 22-13-21 | D00381A | B09 | | | TB0119G | 38 | 2 | | ALL |
| 223R | 24 | PW | IW | | 0-0 | 22-13-21 | D00381A | A09 | | | TB0119G | 37 | 2 | | ALL |
| 223Z | | | IW | | 0-0 | 22-13-21 | D00381A | DED | | | GDY0007 | S.. | 2 | | ALL |
| 224 | 20 | UA | | | 1-6 | 22-13-21 | D00377B | | | GS | GDY0007 | S.. | 2 | | ALL |
| 224B | 24 | PW | IX | | 3-9 | 22-13-21 | D00381B | A02 | | | D00377B | C07 | | | ALL |
| 224R | 24 | PW | IX | | 0-0 | 22-13-21 | D00381B | A01 | | | D00377B | B07 | | | ALL |
| 224Z | | | IX | | 0-0 | 22-13-21 | D00381B | DED | | | D00377B | | | GS | ALL |
| 225 | 20 | UA | | | 1-6 | 22-13-21 | GDY0006 | S.. | 2 | | D00381B | | | FE | ALL |
| 225B | 24 | PW | IY | | 3-2 | 22-13-21 | D00381B | E02 | | | D05619J | 5 | | | ALL |
| 225R | 24 | PW | IY | | 0-0 | 22-13-21 | D00381B | E01 | | | D05619J | 4 | | | ALL |
| 225Z | | | IY | | 0-0 | 22-13-21 | D00381B | | | FE | D05619J | 6 | | | ALL |
| 226B | 22 | PB | JA | | 4-9 | 22-13-21 | D00381B | E06 | | | D04529P | 4 | | | ALL |
| 226R | 22 | PB | JA | | 0-0 | 22-13-21 | D00381B | F06 | | | D04529P | 3 | | | ALL |
| 227B | 22 | PB | JB | | 4-10 | 22-13-21 | D04385P | 18 | | | D00381B | E07 | | | ALL |
| 227R | 22 | PB | JB | | 0-0 | 22-13-21 | D04385P | 17 | | | D00381B | F07 | | | ALL |
| 228B | 24 | PW | JC | | 4-8 | 34-61-24 | D04805P | 3 | | | TB0119G | 38 | 2 | | ALL |
| 228R | 24 | PW | JC | | 0-0 | 34-61-24 | D04805P | 2 | | | TB0119G | 37 | 2 | | ALL |
| 228Z | | | JC | | 0-0 | 34-61-24 | D04805P | 4 | | | GDY0007 | S.. | 2 | | ALL |
| 229B | 24 | PW | JD | | 5-0 | 22-14-21 | D04595P | 11 | | | TB0119H | 3 | 2 | | ALL |
| 229R | 24 | PW | JD | | 0-0 | 22-14-21 | D04595P | 10 | | | TB0119H | 1 | 2 | | ALL |
| 229Z | | | JD | | 0-0 | 22-14-21 | D04595P | 12 | | | GDY0001 | S.. | 2 | | ALL |
| 230 | 20 | UA | | | 1-6 | 22-15-11 | GDY0006 | S.. | 2 | | D00381B | | | FH | ALL |
| 230B | 24 | PW | JE | | 3-9 | 22-15-11 | D04857P | 25 | | | D00381B | F02 | | | ALL |
| 230R | 24 | PW | JE | | 0-0 | 22-15-11 | D04857P | 24 | | | D00381B | F01 | | | ALL |
| 230Z | | | JE | | 0-0 | 22-15-11 | D04857P | 26 | | | D00381B | | | FH | ALL |
| 231B | 24 | PW | JF | | 2-8 | 22-15-11 | D00381A | E01 | | | TB0119G | 144 | 2 | | ALL |
| 231R | 24 | PW | JF | | 0-0 | 22-15-11 | D00381A | D01 | | | TB0119G | 143 | 2 | | ALL |
| 231Z | | | JF | | 0-0 | 22-15-11 | D00381A | DED | | | GDY0007 | S.. | 2 | | 050-099, 277-299 |
| 231Z | | | JF | | 0-0 | 22-15-11 | D00381A | DED | | | GDY0008 | S.. | 2 | | 150-199, 275-276 |
| 232 | 20 | UA | | | 1-6 | 22-15-11 | GDY0005 | S.. | 2 | | D00381B | | | FI | ALL |
| 232B | 24 | PW | JG | | 3-0 | 22-15-11 | D00381B | F03 | | | D05617P | 11 | | | ALL |
| 232R | 24 | PW | JG | | 0-0 | 22-15-11 | D00381B | E03 | | | D05617P | 10 | | | ALL |
| 232Z | | | JG | | 0-0 | 22-15-11 | D00381B | | | FI | D05617P | 12 | | | ALL |
| 233B | 24 | PW | JH | | 3-3 | 22-15-11 | D00381A | H03 | | | TB0119G | 154 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 25

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|----------|-------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | | |
| 233R | 24 | PW | JH | 0-0 | 22-15-11 | | D00381A | G03 | | | | TB0119G | 153 | 2 | | ALL |
| 233Z | | | JH | 0-0 | 22-15-11 | | D00381A | DED | | | | GDY0009 | S.. | 2 | | ALL |
| 235B | 24 | PW | JJ | 4-10 | 22-32-12 | | D04857P | 14 | | | | TB0119H | 3 | 2 | | ALL |
| 235R | 24 | PW | JJ | 0-0 | 22-32-12 | | D04857P | 13 | | | | TB0119H | 1 | 2 | | ALL |
| 235Z | | | JJ | 0-0 | 22-32-12 | | D04857P | 15 | | | | GDY0001 | S.. | 2 | | ALL |
| 237B | 24 | PW | JL | 6-0 | 22-22-21 | | D04361P | 8 | | | | TB0119G | 35 | 2 | | ALL |
| 237R | 24 | PW | JL | 0-0 | 22-22-21 | | D04361P | 7 | | | | TB0119G | 34 | 2 | | ALL |
| 237Z | | | JL | 0-0 | 22-22-21 | | D04361P | 9 | | | | GDY0006 | S.. | 2 | | ALL |
| 238 | 20 | UA | | 1-6 | 22-41-11 | | D00381B | | | | GJ | GDX0006 | S.. | 2 | | ALL |
| 238B | 24 | PW | JM | 4-6 | 22-41-11 | | D00381B | C04 | | | | D04873P | 4 | | | ALL |
| 238R | 24 | PW | JM | 0-0 | 22-41-11 | | D00381B | C03 | | | | D04873P | 3 | | | ALL |
| 238Z | | | JM | 0-0 | 22-41-11 | | D00381B | | | | GJ | D04873P | 5 | | | ALL |
| 239B | 24 | PW | JN | 2-8 | 22-41-12 | | D00381A | A02 | | | | TB0119F | C129 | 2 | | ALL |
| 239R | 24 | PW | JN | 0-0 | 22-41-12 | | D00381A | A01 | | | | TB0119F | A129 | 2 | | ALL |
| 239Z | | | JN | 0-0 | 22-41-12 | | GDY0006 | S.. | 2 | | | D00381A | DED | | | ALL |
| 240B | 24 | PW | JO | 3-10 | 34-12-22 | | D04805P | 30 | | | | TB0119H | 67 | 2 | | ALL |
| 240R | 24 | PW | JO | 0-0 | 34-12-22 | | D04805P | 29 | | | | TB0119H | 65 | 2 | | ALL |
| 240Z | | | JO | 0-0 | 34-12-22 | | D04805P | 31 | | | | GDY0010 | S.. | 2 | | 050-099, 277-299 |
| 240Z | | | JO | 0-0 | 34-12-22 | | D04805P | 31 | | | | GDY0011 | S.. | 2 | | 150-199, 275-276 |
| 241B | 24 | PW | JP | 4-4 | 27-11-22 | | D04361P | 24 | | | | TB0119H | 67 | 2 | | ALL |
| 241R | 24 | PW | JP | 0-0 | 27-11-22 | | D04361P | 23 | | | | TB0119H | 65 | 2 | | ALL |
| 241Z | | | JP | 0-0 | 27-11-22 | | D04361P | 15 | | | | GDY0010 | S.. | 2 | | 050-099, 277-299 |
| 241Z | | | JP | 0-0 | 27-11-22 | | D04361P | 15 | | | | GDY0011 | S.. | 2 | | 150-199, 275-276 |
| 243B | 24 | PW | JR | 6-4 | 34-61-22 | | D04805P | 23 | | | | TB0119H | 3 | 2 | | ALL |
| 243R | 24 | PW | JR | 0-0 | 34-61-22 | | D04805P | 24 | | | | TB0119H | 1 | 2 | | ALL |
| 243Z | | | JR | 0-0 | 34-61-22 | | D04805P | 25 | | | | GDY0001 | S.. | 2 | | ALL |
| 248B | 24 | PL | JW | 5-2 | 22-12-21 | | D04361P | 12 | | | | D00381B | F13 | | | ALL |
| 248R | 24 | PL | JW | 0-0 | 22-12-21 | | D04361P | 11 | | | | D00381B | E13 | | | ALL |
| 250B | 24 | PW | JY | 2-11 | 34-22-38 | | D05617P | 51 | | | | TB0119G | 6 | 2 | | ALL |
| 250R | 24 | PW | JY | 0-0 | 34-22-38 | | D05617P | 50 | | | | TB0119G | 5 | 2 | | ALL |
| 250Z | | | JY | 0-0 | 34-22-38 | | D05617P | 52 | | | | GDY0001 | S.. | 2 | | ALL |
| 251B | 24 | PL | KA | 3-6 | 23-51-13 | | D00377B | B01 | | | | D05505P | 3 | | | ALL |
| 251R | 24 | PL | KA | 0-0 | 23-51-13 | | D00377B | A01 | | | | D05505P | 2 | | | ALL |
| 252B | 24 | PW | KB | 5-0 | 34-31-21 | | D00377B | C11 | | | | TB0119Y | C008 | BJ | | ALL |
| 252R | 24 | PW | KB | 0-0 | 34-31-21 | | D00377B | B11 | | | | TB0119Y | A008 | BJ | | ALL |
| 252Z | | | KB | 0-0 | 34-31-21 | | D00377B | DED | | | | GDY0002 | S.. | 2 | | ALL |
| 253B | 24 | PW | KC | 4-9 | 34-22-91 | | D04455P | 17 | | | | TB0119G | 29 | 2 | | 050-099, 150-156, 162-166 |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 26

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | |
| 253R | 24 | PW | KC | 0-0 | 34-22-91 | D04455P | | 16 | | | TB0119G | 28 | 2 | | 050-099, 150-156, 162-166 |
| 253Z | | | KC | 0-0 | 34-22-91 | D04455P | | 18 | | | GDY0006 | S.. | 2 | | 050-099, 150-156, 162-166 |
| 254B | 22 | PB | KD | 5-2 | 34-31-21 | D00377B | | C15 | | | D04369P | 8 | | | ALL |
| 254R | 22 | PB | KD | 0-0 | 34-31-21 | D00377B | | B15 | | | D04369P | 9 | | | ALL |
| 255B | 24 | PW | KE | 4-10 | 34-22-28 | D04857P | | 21 | | | TB0119G | 6 | 2 | | ALL |
| 255R | 24 | PW | KE | 0-0 | 34-22-28 | D04857P | | 20 | | | TB0119G | 5 | 2 | | ALL |
| 255Z | | | KE | 0-0 | 34-22-28 | D04857P | | 22 | | | GDY0001 | S.. | 2 | | ALL |
| 256B | 24 | PW | KF | 4-9 | 34-31-21 | D04369P | | 7 | | | TB0119G | 73 | 2 | | ALL |
| 256R | 24 | PW | KF | 0-0 | 34-31-21 | D04369P | | 6 | | | TB0119G | 72 | 2 | | ALL |
| 256Z | | | KF | 0-0 | 34-31-21 | D04369P | | 12 | | | GDY0011 | S.. | 2 | | ALL |
| 257B | 24 | PW | KG | 3-9 | 34-31-21 | D04805P | | 33 | | | TB0119G | 73 | 2 | | ALL |
| 257R | 24 | PW | KG | 0-0 | 34-31-21 | D04805P | | 32 | | | TB0119G | 72 | 2 | | ALL |
| 257Z | | | KG | 0-0 | 34-31-21 | D04805P | | 34 | | | GDY0011 | S.. | 2 | | ALL |
| 258B | 24 | PW | KH | 2-11 | 34-31-21 | D00377B | | C13 | | | TB0119G | 73 | 2 | | ALL |
| 258R | 24 | PW | KH | 0-0 | 34-31-21 | D00377B | | B13 | | | TB0119G | 72 | 2 | | ALL |
| 258Z | | | KH | 0-0 | 34-31-21 | D00377B | | DED | | | GDY0011 | S.. | 2 | | ALL |
| 259B | 24 | PW | KI | 6-0 | 34-22-91 | D04455P | | 20 | | | TB0119G | 13 | 2 | | ALL |
| 259R | 24 | PW | KI | 0-0 | 34-22-91 | D04455P | | 19 | | | TB0119G | 12 | 2 | | ALL |
| 259Z | | | KI | 0-0 | 34-22-91 | D04455P | | 21 | | | GDY0002 | S.. | 2 | | ALL |
| 263B | 24 | PW | KM | 6-2 | 34-22-29 | D04805P | | 18 | | | TB0119G | 13 | 2 | | ALL |
| 263R | 24 | PW | KM | 0-0 | 34-22-29 | D04805P | | 17 | | | TB0119G | 12 | 2 | | ALL |
| 263Z | | | KM | 0-0 | 34-22-29 | D04805P | | 19 | | | GDY0002 | S.. | 2 | | ALL |
| 264B | 24 | PW | KN | 4-10 | 34-22-29 | D04805P | | 21 | | | TB0119G | 29 | 2 | | ALL |
| 264R | 24 | PW | KN | 0-0 | 34-22-29 | D04805P | | 20 | | | TB0119G | 28 | 2 | | ALL |
| 264Z | | | KN | 0-0 | 34-22-29 | D04805P | | 22 | | | GDY0006 | S.. | 2 | | ALL |
| 280B | 24 | PW | LE | 3-3 | 34-22-28 | D05619J | | 2 | | | TB0119G | 31 | 2 | | ALL |
| 280R | 24 | PW | LE | 0-0 | 34-22-28 | D05619J | | 1 | | | TB0119G | 30 | 2 | | ALL |
| 280Z | | | LE | 0-0 | 34-22-28 | D05619J | | 3 | | | GDY0006 | S.. | 2 | | ALL |
| 281B | 24 | PW | LF | 3-11 | 34-22-38 | D05617P | | 27 | | | TB0119G | 55 | 2 | | ALL |
| 281R | 24 | PW | LF | 0-0 | 34-22-38 | D05617P | | 26 | | | TB0119G | 54 | 2 | | ALL |
| 281Z | | | LF | 0-0 | 34-22-38 | D05617P | | 28 | | | GDY0009 | S.. | 2 | | ALL |
| 282B | 24 | PW | LG | 3-1 | 34-22-39 | D05617P | | 14 | | | TB0119G | 29 | 2 | | ALL |
| 282R | 24 | PW | LG | 0-0 | 34-22-39 | D05617P | | 13 | | | TB0119G | 28 | 2 | | ALL |
| 282Z | | | LG | 0-0 | 34-22-39 | D05617P | | 15 | | | GDY0006 | S.. | 2 | | ALL |
| 283B | 24 | PW | LH | 2-10 | 34-22-39 | D05617P | | 17 | | | TB0119G | 13 | 2 | | ALL |
| 283R | 24 | PW | LH | 0-0 | 34-22-39 | D05617P | | 16 | | | TB0119G | 12 | 2 | | ALL |
| 283Z | | | LH | 0-0 | 34-22-39 | D05617P | | 37 | | | GDY0002 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 27

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|-----|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | | | |
| 284B | 24 | PW | LI | | 4-6 | 34-22-38 | D05617P | | 39 | | | | TB0119Y | C081 | BJ | | ALL |
| 284R | 24 | PW | LI | | 0-0 | 34-22-38 | D05617P | | 38 | | | | TB0119Y | A081 | BJ | | ALL |
| 284Z | | | LI | | 0-0 | 34-22-38 | D05617P | | 40 | | | | GDY0012 | S.. | 2 | | ALL |
| 285B | 24 | PW | LJ | | 5-0 | 34-43-21 | D04849P | | 3 | | | | TB0119H | 63 | 2 | | ALL |
| 285R | 24 | PW | LJ | | 0-0 | 34-43-21 | D04849P | | 2 | | | | TB0119H | 61 | 2 | | ALL |
| 285Z | | | LJ | | 0-0 | 34-43-21 | D04849P | | 4 | | | | GDY0010 | S.. | 2 | | ALL |
| 286B | 24 | PW | LK | | 3-11 | 34-61-24 | D04805P | | 6 | | | | TB0119H | 63 | 2 | | ALL |
| 286R | 24 | PW | LK | | 0-0 | 34-61-24 | D04805P | | 5 | | | | TB0119H | 61 | 2 | | ALL |
| 286Z | | | LK | | 0-0 | 34-61-24 | D04805P | | 7 | | | | GDY0010 | S.. | 2 | | ALL |
| 287B | 24 | PW | LL | | 4-10 | 34-22-29 | D04857P | | 7 | | | | TB0119F | C007 | 2 | | ALL |
| 287R | 24 | PW | LL | | 0-0 | 34-22-29 | D04857P | | 6 | | | | TB0119F | A007 | 2 | | ALL |
| 287Z | | | LL | | 0-0 | 34-22-29 | D04857P | | 8 | | | | GDY0001 | S.. | 2 | | ALL |
| 289B | 24 | PW | LN | | 6-4 | 34-61-22 | D04805P | | 27 | | | | TB0119Y | C008 | BJ | | ALL |
| 289R | 24 | PW | LN | | 0-0 | 34-61-22 | D04805P | | 26 | | | | TB0119Y | A008 | BJ | | ALL |
| 289Z | | | LN | | 0-0 | 34-61-22 | D04805P | | 28 | | | | GDY0002 | S.. | 2 | | ALL |
| 290B | 22 | PB | LO | | 3-11 | 27-41-21 | D04361P | | 22 | | | | D04883P | 5 | | | ALL |
| 290R | 22 | PB | LO | | 0-0 | 27-41-21 | D04361P | | 21 | | | | D04883P | 4 | | | ALL |
| 296B | 24 | PW | LU | | 3-11 | 34-22-34 | D05617P | | 24 | | | | TB0119H | 63 | 2 | | ALL |
| 296R | 24 | PW | LU | | 0-0 | 34-22-34 | D05617P | | 23 | | | | TB0119H | 61 | 2 | | ALL |
| 296Z | | | LU | | 0-0 | 34-22-34 | D05617P | | 25 | | | | GDY0010 | S.. | 2 | | ALL |
| 297B | 24 | PW | LV | | 4-3 | 34-22-92 | D04393P | | 2 | | | | TB0119G | 31 | 2 | | ALL |
| 297R | 24 | PW | LV | | 0-0 | 34-22-92 | D04393P | | 1 | | | | TB0119G | 30 | 2 | | ALL |
| 297Z | | | LV | | 0-0 | 34-22-92 | D04393P | | 3 | | | | GDY0006 | S.. | 2 | | ALL |
| 298B | 24 | PW | LW | | 4-2 | 34-22-28 | D04805P | | 9 | | | | TB0119G | 55 | 2 | | ALL |
| 298R | 24 | PW | LW | | 0-0 | 34-22-28 | D04805P | | 8 | | | | TB0119G | 54 | 2 | | ALL |
| 298Z | | | LW | | 0-0 | 34-22-28 | D04805P | | 10 | | | | GDY0009 | S.. | 2 | | ALL |
| 299 | 20 | UA | | | 1-6 | 34-22-81 | D05619J | | | | GD | | GDX0002 | S.. | 2 | | ALL |
| 299B | 24 | PW | LX | | 5-3 | 34-22-81 | D04455P | | 14 | | | | D05619J | 17 | | | ALL |
| 299R | 24 | PW | LX | | 0-0 | 34-22-81 | D04455P | | 13 | | | | D05619J | 19 | | | ALL |
| 299Z | | | LX | | 0-0 | 34-22-81 | D04455P | | 15 | | | | D05619J | | | GD | ALL |
| 302B | 22 | PC | MB | | 4-10 | 22-12-21 | D00381A | | H10 | | | | D04385P | 15 | | | ALL |
| 302R | 22 | PC | MB | | 0-0 | 22-12-21 | D00381A | | J09 | | | | D04385P | 14 | | | ALL |
| 302Y | 22 | PC | MB | | 0-0 | 22-12-21 | D00381A | | H09 | | | | D04385P | 16 | | | ALL |
| 303B | 22 | PC | MC | | 4-7 | 22-12-21 | D00381B | | H10 | | | | D04385P | 12 | | | ALL |
| 303R | 22 | PC | MC | | 0-0 | 22-12-21 | D00381B | | J09 | | | | D04385P | 11 | | | ALL |
| 303Y | 22 | PC | MC | | 0-0 | 22-12-21 | D00381B | | H09 | | | | D04385P | 13 | | | ALL |
| 305B | 22 | PC | ME | | 4-8 | 22-13-21 | D04529P | | 6 | | | | D00381B | K06 | | | ALL |
| 305R | 22 | PC | ME | | 0-0 | 22-13-21 | D04529P | | 5 | | | | D00381B | J05 | | | ALL |
| 305Y | 22 | PC | ME | | 0-0 | 22-13-21 | D04529P | | 7 | | | | D00381B | K05 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 28

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | |
| 306B | 22 | PC | MF | | 4-9 | 22-13-21 | D04529P | | 9 | | D00381A | K06 | | | ALL |
| 306R | 22 | PC | MF | | 0-0 | 22-13-21 | D04529P | | 8 | | D00381A | J05 | | | ALL |
| 306Y | 22 | PC | MF | | 0-0 | 22-13-21 | D04529P | | 10 | | D00381A | K05 | | | ALL |
| 307B | 22 | PC | MG | | 4-7 | 22-13-21 | D04385P | | 20 | | D00381B | J06 | | | ALL |
| 307R | 22 | PC | MG | | 0-0 | 22-13-21 | D04385P | | 19 | | D00381B | H06 | | | ALL |
| 307Y | 22 | PC | MG | | 0-0 | 22-13-21 | D04385P | | 21 | | D00381B | H05 | | | ALL |
| 308B | 22 | PC | MH | | 4-10 | 22-13-21 | D04385P | | 23 | | D00381A | J06 | | | ALL |
| 308R | 22 | PC | MH | | 0-0 | 22-13-21 | D04385P | | 22 | | D00381A | H06 | | | ALL |
| 308Y | 22 | PC | MH | | 0-0 | 22-13-21 | D04385P | | 24 | | D00381A | H05 | | | ALL |
| 310B | 24 | PM | MJ | | 5-4 | 27-58-21 | D04883P | | 27 | | D04385P | 46 | | | ALL |
| 310R | 24 | PM | MJ | | 0-0 | 27-58-21 | D04883P | | 28 | | D04385P | 47 | | | ALL |
| 310Y | 24 | PM | MJ | | 0-0 | 27-58-21 | D04883P | | 29 | | D04385P | 48 | | | ALL |
| 311B | 24 | PM | MK | | 2-5 | 34-12-11 | D04393P | | 33 | | D04857P | 11 | | | ALL |
| 311R | 24 | PM | MK | | 0-0 | 34-12-11 | D04393P | | 32 | | D04857P | 4 | | | ALL |
| 311Y | 24 | PM | MK | | 0-0 | 34-12-11 | D04393P | | 34 | | D04857P | 12 | | | ALL |
| 501B | 24 | PW | UA | | 2-11 | 34-43-21 | D05619J | | 9 | | D04849P | 9 | | | ALL |
| 501R | 24 | PW | UA | | 0-0 | 34-43-21 | D05619J | | 8 | | D04849P | 8 | | | ALL |
| 501Z | | | UA | | 0-0 | 34-43-21 | D05619J | | 10 | | D04849P | 10 | | | ALL |
| 502W | 24 | 7K | UB | | 3-0 | 34-43-21 | D05617P | | 1 | | TB0211G | 9 | 2 | | ALL |
| 502WB | 24 | 7K | UB | | 0-0 | 34-43-21 | D05617P | | 2 | | TB0211G | 3 | 2 | | 050-099, 150-199, 275-278 |
| 502WB | 24 | 7K | UB | | 0-0 | 34-43-21 | D05617P | | 2 | | TB0211G | 8 | 2 | | 280-299 |
| 502Z | | | UB | | 0-0 | 34-43-21 | D05617P | | 3 | | GDZ0001 | S.. | 2 | | ALL |
| 503W | 24 | 7K | UC | | 3-4 | 34-43-21 | D04849P | | 5 | | TB0211G | 9 | 2 | | 050-099, 151 |
| 503WB | 24 | 7K | UC | | 0-0 | 34-43-21 | D04849P | | 6 | | TB0211G | 8 | 2 | | 050-099, 151 |
| 503Z | | | UC | | 0-0 | 34-43-21 | D04849P | | 7 | | GDZ0001 | S.. | 2 | | 050-099, 151 |
| 505B | 24 | PW | UE | | 3-4 | 34-22-38 | D05617P | | 48 | | TB0119G | 31 | 2 | | ALL |
| 505R | 24 | PW | UE | | 0-0 | 34-22-38 | D05617P | | 47 | | TB0119G | 30 | 2 | | ALL |
| 505Z | | | UE | | 0-0 | 34-22-38 | D05617P | | 49 | | GDY0006 | S.. | 2 | | ALL |
| 509B | 24 | PW | UI | | 3-6 | 34-22-29 | D05619J | | 12 | | TB0119F | C136 | 2 | | ALL |
| 509R | 24 | PW | UI | | 0-0 | 34-22-29 | D05619J | | 11 | | TB0119F | A136 | 2 | | ALL |
| 509Z | | | UI | | 0-0 | 34-22-29 | D05619J | | 13 | | GDY0007 | S.. | 2 | | ALL |
| 510B | 24 | PW | UJ | | 3-7 | 27-32-21 | D04325P | | 23 | | TB0119H | 158 | 2 | | ALL |
| 510R | 24 | PW | UJ | | 0-0 | 27-32-21 | D04325P | | 22 | | TB0119H | 156 | 2 | | ALL |
| 510Z | | | UJ | | 0-0 | 27-32-21 | D04325P | | 24 | | GDY0009 | S.. | 2 | | ALL |
| 511B | 24 | PL | UK | | 4-9 | 27-32-21 | D04361P | | 6 | | D04325P | 18 | | | ALL |
| 511R | 24 | PL | UK | | 0-0 | 27-32-21 | D04361P | | 2 | | D04325P | 17 | | | ALL |
| 512B | 24 | PW | UL | | 3-9 | 34-22-39 | D05617P | | 7 | | TB0119H | 158 | 2 | | ALL |
| 512R | 24 | PW | UL | | 0-0 | 34-22-39 | D05617P | | 6 | | TB0119H | 156 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0110
Page 29
May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | | | |
| 512Z | | | UL | 0-0 | 34-22-39 | D05617P | | 8 | | | | | GDY0009 | S.. | 2 | | ALL |
| 542B | 24 | PW | VQ | 2-6 | 31-31-20 | D04873P | | 7 | | | | | TB0119Z | 177 | % | | ALL |
| 542R | 24 | PW | VQ | 0-0 | 31-31-20 | D04873P | | 6 | | | | | TB0119Z | 176 | % | | ALL |
| 542Z | | | VQ | 0-0 | 31-31-20 | D04873P | | 8 | | | | | GDY0011 | S.. | 2 | | 050-099, 150-199, 275-278 280-299 |
| 542Z | | | VQ | 0-0 | 31-31-20 | D04873P | | 8 | | | | | GDY0012 | S.. | 2 | | 280-299 |
| 543B | 24 | PW | VR | 5-0 | 31-31-20 | D04873P | | 21 | | | | | TB0119Y | C008 | BJ | | ALL |
| 543R | 24 | PW | VR | 0-0 | 31-31-20 | D04873P | | 20 | | | | | TB0119Y | A008 | BJ | | ALL |
| 543Z | | | VR | 0-0 | 31-31-20 | D04873P | | 22 | | | | | GDY0002 | S.. | 2 | | ALL |
| 544 | 20 | UA | | 1-6 | 31-35-13 | D00381B | | REF | | VS | | | GDY0006 | S.. | 2 | | ALL |
| 544B | 24 | PW | VS | 3-9 | 31-35-13 | D00381B | | D02 | | | | | D04857P | 43 | | | ALL |
| 544R | 24 | PW | VS | 0-0 | 31-35-13 | D00381B | | D01 | | | | | D04857P | 42 | | | ALL |
| 544Z | | | VS | 0-0 | 31-35-13 | D00381B | | REF | | VS | | | D04857P | 34 | | | ALL |
| 550B | 24 | PW | VY | 3-5 | 34-61-26 | D04805P | | 12 | | | | | TB0119Y | C081 | BJ | | ALL |
| 550R | 24 | PW | VY | 0-0 | 34-61-26 | D04805P | | 11 | | | | | TB0119Y | A081 | BJ | | ALL |
| 550Z | | | VY | 0-0 | 34-61-26 | D04805P | | 13 | | | | | GDY0012 | S.. | 2 | | ALL |
| 558B | 24 | PW | WH | 4-10 | 34-45-14 | D04857P | | 53 | | | | | TB0119G | 102 | 2 | | 050-099, 150-156, 162-166 |
| 558B | 24 | PW | WH | 4-10 | 34-45-14 | D04857P | | 53 | | | | | TB0119Y | C101 | BJ | | 157, 167-199, 277-299 |
| 558R | 24 | PW | WH | 0-0 | 34-45-14 | D04857P | | 52 | | | | | TB0119G | 101 | 2 | | 050-099, 150-156, 162-166 |
| 558R | 24 | PW | WH | 0-0 | 34-45-14 | D04857P | | 52 | | | | | TB0119Y | A101 | BJ | | 157, 167-199, 277-299 |
| 558Z | | | WH | 0-0 | 34-45-14 | D04857P | | 54 | | | | | GDY0001 | S.. | 2 | | 050-099, 150-199, 277-299 |
| 559B | 24 | PW | WI | 6-1 | 34-45-14 | D04455P | | 2 | | | | | TB0119G | 102 | 2 | | 050-099, 150-156, 162-166 |
| 559B | 24 | PW | WI | 6-1 | 34-45-14 | D04455P | | 2 | | | | | TB0119Y | C101 | BJ | | 157, 167-199, 277-299 |
| 559R | 24 | PW | WI | 0-0 | 34-45-14 | D04455P | | 1 | | | | | TB0119G | 101 | 2 | | 050-099, 150-156, 162-166 |
| 559R | 24 | PW | WI | 0-0 | 34-45-14 | D04455P | | 1 | | | | | TB0119Y | A101 | BJ | | 157, 167-199, 277-299 |
| 559Z | | | WI | 0-0 | 34-45-14 | D04455P | | 3 | | | | | GDY0001 | S.. | 2 | | 050-099, 150-199, 277-299 |
| 601 | 22 | PA | | 3-6 | 31-31-18 | D04361P | | 17 | | | | | D04805P | 43 | | | ALL |
| 602 | 22 | PA | | 3-6 | 31-31-18 | D04361P | | 18 | | | | | D04805P | 44 | | | ALL |
| 603 | 22 | PA | | 3-6 | 31-31-18 | D04361P | | 19 | | | | | D04805P | 45 | | | ALL |
| 604 | 22 | PA | | 3-6 | 31-31-18 | D04361P | | 20 | | | | | D04805P | 46 | | | ALL |
| 605 | 24 | PK | | 1-6 | 22-11-22 | D00381A | | B11 | | | | | D00381A | B12 | | | 050-099 |
| 607 | 24 | PK | | 3-0 | 22-11-22 | D00381A | | D04 | | | | | D00381B | A04 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 30

May 20/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | |
| 608Y | 22 | | PJ | | 3-0 | 27-41-21 | D04361P | | | | D04385P | | 53 | | 050-099, 150-154, 163-165, 275-276 |
| 608Y | 22 | | PJ | | 3-6 | 27-41-21 | D04361P | | | | D04385P | | 53 | | 155-162, 166-199, 277-299 |
| 609 | 22 | | PA | | 3-11 | 27-41-21 | D04361P | | | | D04883P | | 16 | | ALL |
| 612 | 22 | | PA | | 2-9 | 34-22-36 | D05617P | | | | TB0119G | | 110 | 2 | ALL |
| 613 | 22 | | PA | | 4-9 | 34-22-26 | D04793P | | | | TB0119F | A117 | 2 | | ALL |
| 620 | 24 | | PK | | 1-6 | 22-11-22 | D00381B | B12 | | | D00381B | D15 | | | ALL |
| 621 | 24 | | PK | | 1-6 | 22-11-22 | D00381B | A12 | | | D00381B | B15 | | | ALL |
| 632 | 24 | | PK | | 1-6 | 22-11-22 | D00381A | C11 | | | D00381A | C12 | | | ALL |
| 634 | 24 | | PK | | 1-6 | 22-11-22 | D00381B | J02 | | | D00381B | J04 | | | ALL |
| 635 | 22 | | PA | | 4-2 | 34-22-13 | D04873P | | | 1 | TB0119G | | 125 | 2 | ALL |
| 688 | 24 | | PK | | 4-7 | SPARE | D04447P | | | 1 | TB0119H | | 164 | # | 150-199 |
| 697 | 22 | | PA | | 4-10 | 34-45-14 | D04857P | | | 23 | TB0119Y | A102 | BJ | | 157, 167-199, 277-299 |
| 70K | 20 | | PA | | 4-0 | 29-11-14 | D04793P | | | 24 | D04385P | | 52 | | 050-099, 150-199, 275-278 |
| 70K | 20 | | PA | | 4-2 | 29-11-14 | D04793P | | | 24 | D04385P | | 52 | | 280-299 |
| 70M | 20 | | PA | | 4-0 | 29-11-14 | D04793P | | | 23 | D04385P | | 51 | | ALL |
| 801 | 20 | | PA | | 4-0 | 38-32-11 | D04325P | | | 5 | D04793P | | 7 | | 050-099, 150-199, 277-278 |
| 801 | 20 | | PA | | 2-10 | SPARE | D04325P | | | 5 | D04793P | | 7 | | 276 |
| 801 | 20 | | PA | | 4-2 | 38-32-11 | D04325P | | | 5 | D04793P | | 7 | | 280-299 |
| 901B | 22 | | PR | AL | 5-0 | 23-32-21 | D09314 | | | 15 | D05637P | | 9 | | 150, 152-199 |
| 901R | 22 | | PR | AL | 0-0 | 23-32-21 | D09314 | | | 14 | D05637P | | 10 | | 150, 152-199 |
| 901Z | | | | AL | 0-0 | 23-32-21 | D09314 | DED | | | D05637P | | | FL | 150, 152-199 |
| 902 | 20 | | PQ | AM | 5-0 | 23-32-21 | TB0119G | | 2 | 160 | D05637P | | 12 | | 150, 152-156, 162-199 |
| 902 | 20 | | PQ | AM | 5-0 | 23-32-21 | SP00006 | | S | | D05637P | | 12 | | 157 |
| 902Z | | | | AM | 0-0 | 23-32-21 | TB0119G | DED | | | D05637P | | | FL | 150, 152-156, 162-199 |
| 902Z | | | | AM | 0-0 | 23-32-21 | SP00006 | DED | | | D05637P | | | FL | 157 |
| 903 | 22 | | PA | | 5-0 | 23-32-21 | D09314 | | | 20 | D05637P | | 7 | | 150, 152-199 |
| 904 | 22 | | PA | | 5-0 | 23-32-21 | TB0119G | | 2 | 160 | D09314 | | 5 | | 150, 152-156, 162-199 |
| 904 | 22 | | PA | | 5-0 | 23-32-21 | SP00006 | | S | | D09314 | | 5 | | 157 |
| 908B | 24 | | PW | AC | 0-0 | 34-53-21 | D04325P | | | 9 | TB0119G | | 38 | 2 | 275-278 |
| 908B | 24 | | PW | AM | 5-0 | 34-53-21 | D04325P | | | 9 | TB0119G | | 38 | 2 | 280-299 |
| 908R | 24 | | PW | AC | 5-0 | 34-53-21 | D04325P | | | 8 | TB0119G | | 37 | 2 | 275-278 |
| 908R | 24 | | PW | AM | 0-0 | 34-53-21 | D04325P | | | 8 | TB0119G | | 37 | 2 | 280-299 |
| 908Z | | | | AC | 0-0 | 34-53-21 | D04325P | | | 10 | GDY0007 | | S.. | 2 | 275-278 |
| 908Z | | | | AM | 0-0 | 34-53-21 | D04325P | | | 10 | GDY0007 | | S.. | 2 | 280-299 |
| 911B | 22 | | PR | AO | 5-0 | 23-32-21 | D09314 | | | 2 | D04393P | | 20 | | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W0110

Page 31

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|---------|-------------|----|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0119 | 286T0119 | | | E1-5 SHELF R (continued) | | | | | | | | | | | | | |
| 911R | 22 | PR | AO | 0-0 | 23-32-21 | D09314 | | 1 | | | | | D04393P | 19 | | | 150, 152-199 |
| 911Z | | | AO | 0-0 | 23-32-21 | D09314 | | DED | | | | | D04393P | 18 | | | 150, 152-199 |
| 912B | 22 | PR | I | 5-0 | 23-32-21 | D09314 | | 4 | | | | | D04393P | 22 | | | 150, 152-199 |
| 912R | 22 | PR | I | 0-0 | 23-32-21 | D09314 | | 3 | | | | | D04393P | 21 | | | 150, 152-199 |
| 912Z | | | I | 0-0 | 23-32-21 | D09314 | | | | | | | D04393P | 23 | | | 150, 152-199 |
| 913 | 20 | PA | | 5-0 | 23-32-21 | TB0119G | | 160 | 2 | | | FU | D04393P | 24 | | | 150, 152-156, 162-199 |
| 914 | 22 | PA | | 5-0 | 23-32-21 | D09314 | | 6 | | | | | D04393P | 25 | | | 150, 152-199 |
| 915 | 22 | PA | | 5-0 | 23-32-21 | D09314 | | 7 | | | | | D04393P | 26 | | | 150, 152-199 |
| 917 | 22 | PA | | 3-0 | 23-32-21 | D09314 | | 21 | | | | | GDX0011 | S.. | 2 | | 150, 152-156, 162-199 |
| 917 | 22 | PA | | 3-0 | 23-32-21 | D09314 | | 21 | | | | | GDX0004 | S.. | 2 | | 157 |
| 918 | 22 | PA | | 3-0 | 23-32-21 | D09314 | | 22 | | | | | GDX0011 | S.. | 2 | | 150, 152-156, 162-199 |
| 918 | 22 | PA | | 3-0 | 23-32-21 | D09314 | | 22 | | | | | GDX0004 | S.. | 2 | | 157 |
| 919 | 20 | PA | | 3-0 | 23-32-21 | D09314 | | | | | | | GDX0004 | S.. | 2 | | 150, 152-199 |
| FRA | | | | 0-0 | 34-22-81 | D05619J | | | | | | | GD | D05619J | 21 | | 050-099, 150-199, 275-278 |
| FRA | | | | 1-3 | 34-22-81 | D05619J | | | | | | | GD | D05619J | 21 | | 280-299 |
| FRL | | | | 0-0 | 23-32-21 | D05637P | | 8 | | | | | | | | FL | 150, 152-199 |

WIRE LIST
D280T132

91-21-11
Section W0110
Page 32 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0120 | 286T0120 | | | AFT CABIN GALLEY SPEAKER HINGED PANEL (P) | | | | | | | | | | | |
| 033 | 22 | | PA | | 7-0 | 33-25-11 | D05353P | | 3 | | L00636 | = P | \$ | | 050-099 |
| 034 | 22 | | PA | | 6-0 | 23-34-13 | D05353P | | 2 | | L00637 | = P | | | 050-099 |
| 035 | 22 | | PA | | 7-0 | 23-42-11 | D05353P | | 1 | | L00638 | = P | | | 050-099 |
| 038 | 20 | | PA | | 7-0 | 23-42-11 | D05353P | | 4 | | L00638 | = G | | | 050-099 |
| W0121 | 286T0121 | | | E1-1 SHELF | | | | | | | | | | | |
| 001 | 22 | | PA | | 4-0 | 22-21-11 | D01259B | | C15 | | TB0101G | 51 | 2 | | ALL |
| 002 | 22 | | PA | | 4-0 | 22-21-11 | D05323J | | 1 | | TB0101G | 51 | 2 | | ALL |
| 003 | 22 | | PA | | 3-0 | 27-09-13 | D04357J | | 14 | | TB0101H | 121 | 2 | | ALL |
| 004 | 22 | | PA | | 4-0 | 22-22-11 | D00665B | | J15 | | TB0101G | 54 | 2 | | ALL |
| 005 | 22 | | PA | | 4-0 | 22-22-11 | D05323J | | 2 | | TB0101G | 54 | 2 | | ALL |
| 006 | 22 | | PA | | 3-0 | 22-22-11 | D04357J | | 8 | | TB0101G | 54 | 2 | | ALL |
| 007 | 22 | | PA | | 4-0 | 22-22-11 | D00665B | | J14 | | D04357J | 9 | | | ALL |
| 008 | 22 | | PA | | 4-0 | 22-22-11 | D05323J | | 3 | | D04357J | 7 | | | ALL |
| 009 | 22 | | PA | | 4-0 | 27-09-12 | D05323J | | 6 | | TB0101H | 155 | 2 | | ALL |
| 010 | 22 | | PA | | 4-0 | 27-09-13 | D00829A | | K13 | | TB0101H | 153 | 2 | | ALL |
| 011 | 22 | | PA | | 4-0 | 27-09-13 | D00829A | | J13 | | TB0101H | 151 | 2 | | ALL |
| 012 | 22 | | PA | | 4-0 | 27-09-13 | D00665B | | F06 | | TB0101H | 153 | 2 | | ALL |
| 013 | 22 | | PA | | 4-0 | 27-09-13 | D00665B | | F05 | | TB0101H | 151 | 2 | | ALL |
| 015 | 22 | | PA | | 5-0 | 27-21-12 | D01263B | | A15 | | GDX0008 | D.. | 2 | | ALL |
| 016 | 16 | | PA | | 5-0 | 27-21-12 | D01263C | | 2 | | GDX0008 | S.. | 2 | | ALL |
| 017 | 16 | | PA | | 5-0 | 27-21-12 | D01263C | | 3 | | GDX0008 | D.. | 2 | | ALL |
| 018 | 22 | | PA | | 5-0 | 27-21-12 | D01263B | | D15 | | GDX0008 | D.. | 2 | | ALL |
| 019 | 16 | | PA | | 5-0 | 27-21-12 | D01263C | | 4 | | GDX0008 | D.. | 2 | | ALL |
| 021 | 22 | | PA | | 4-0 | 27-21-12 | D01263B | | C15 | | GDX0004 | D.. | 2 | | ALL |
| 022 | 16 | | PA | | 5-0 | 27-61-14 | D00825C | | 8 | | GDX0009 | D.. | 2 | | ALL |
| 023 | 16 | | PA | | 5-0 | 27-61-14 | D00825C | | 3 | | GDX0009 | D.. | 2 | | ALL |
| 024 | 16 | | PA | | 5-0 | 27-61-14 | D00825C | | 10 | | GDX0009 | S.. | 2 | | ALL |
| 025 | 22 | | PA | | 6-0 | 27-61-14 | D00825B | | F14 | | D01253B | H03 | | | ALL |
| 026 | 22 | | PA | | 6-0 | 27-61-14 | D00825B | | F12 | | D01253B | F03 | | | ALL |
| 027 | 22 | | PA | | 5-0 | 27-61-14 | D00825B | | G14 | | D01251B | H03 | | | ALL |
| 028 | 22 | | PA | | 5-0 | 27-61-14 | D00825B | | G12 | | D01251B | F03 | | | ALL |
| 029 | 16 | | PA | | 5-0 | 27-61-14 | D00825C | | 9 | | GDX0009 | S.. | 2 | | ALL |
| 030 | 16 | | PA | | 4-0 | 27-61-15 | D00827C | | 8 | | GDX0008 | D.. | 2 | | ALL |
| 031 | 16 | | PA | | 4-0 | 27-61-15 | D00827C | | 7 | | GDX0008 | D.. | 2 | | ALL |
| 032 | 16 | | PA | | 4-0 | 27-61-15 | D00827C | | 10 | | GDX0008 | S.. | 2 | | ALL |
| 033 | 22 | | PA | | 6-0 | 27-61-15 | D01251B | | F04 | | D00827A | G03 | | | ALL |
| 034 | 22 | | PA | | 6-0 | 27-61-15 | D01251B | | H04 | | D00827A | G05 | | | ALL |
| 036 | 16 | | PA | | 4-0 | 27-61-15 | D00827C | | 9 | | GDX0008 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0120
Page 1
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0121 | 286T0121 | | | E1-1 SHELF (continued) | | | | | | | | | | | | |
| 037 | 16 | | PA | 4-0 | 27-61-15 | D00827C | | 2 | | | | GDX0008 | D.. | 2 | | ALL |
| 039 | 22 | | PA | 6-0 | 27-61-15 | D00827A | | F05 | | | | D01253B | H04 | | | ALL |
| 040 | 22 | | PA | 6-0 | 27-61-15 | D00827A | | F03 | | | | D01253B | F04 | | | ALL |
| 043 | 16 | | PA | 4-0 | 27-61-16 | D00829C | | 10 | | | | GDX0008 | S.. | 2 | | ALL |
| 044 | 20 | | PA | 4-0 | 27-61-16 | D00829C | | 6 | | | | GDX0008 | D.. | 2 | | ALL |
| 045 | 22 | | PA | 6-0 | 27-61-16 | D01253B | | A07 | | | | D01251B | C07 | | | ALL |
| 046 | 22 | | PA | 2-0 | 27-61-15 | D00827A | | A08 | | | | D00827A | C07 | | | ALL |
| 048 | 22 | | PA | 7-0 | 27-61-16 | D00829B | | G06 | | | | D01251B | H05 | | | ALL |
| 049 | 22 | | PA | 7-0 | 27-61-16 | D00829B | | G04 | | | | D01251B | F05 | | | ALL |
| 051 | 22 | | PA | 5-0 | 27-61-16 | D00829B | | F06 | | | | D01253B | H05 | | | ALL |
| 052 | 22 | | PA | 5-0 | 27-61-16 | D00829B | | F04 | | | | D01253B | F05 | | | ALL |
| 053 | 20 | | PA | 4-0 | 27-61-12 | D00829C | | 4 | | | | GDX0003 | D.. | 2 | | ALL |
| 054 | 16 | | PA | 4-0 | 27-09-11 | D01251C | | 3 | | | | GDX0003 | D.. | 2 | | ALL |
| 055 | 16 | | PA | 4-0 | 27-09-11 | D01251C | | 2 | | | | GDX0003 | D.. | 2 | | ALL |
| 056 | 16 | | PA | 4-0 | 27-09-11 | D01251C | | 8 | | | | GDX0003 | S.. | 2 | | ALL |
| 057 | 16 | | PA | 4-0 | 27-09-11 | D01251C | | 7 | | | | GDX0003 | D.. | 2 | | ALL |
| 058 | 16 | | PA | 4-0 | 27-09-11 | D01251C | | 10 | | | | GDX0003 | D.. | 2 | | ALL |
| 059 | 16 | | PA | 4-0 | 27-09-11 | D01251C | | 9 | | | | GDX0003 | D.. | 2 | | ALL |
| 060 | 16 | | PA | 4-0 | 27-09-11 | D01251C | | 11 | | | | GDX0003 | A.. | 2 | | ALL |
| 061 | 20 | | PA | 4-0 | 27-61-12 | D00827C | | 4 | | | | GDX0003 | D.. | 2 | | ALL |
| 062 | 16 | | PA | 5-0 | 27-09-11 | D01253C | | 3 | | | | GDX0003 | D.. | 2 | | ALL |
| 063 | 16 | | PA | 5-0 | 27-09-11 | D01253C | | 2 | | | | GDX0003 | D.. | 2 | | ALL |
| 064 | 16 | | PA | 5-0 | 27-09-11 | D01253C | | 8 | | | | GDX0003 | S.. | 2 | | ALL |
| 065 | 16 | | PA | 5-0 | 27-09-11 | D01253C | | 7 | | | | GDX0003 | D.. | 2 | | ALL |
| 066 | 16 | | PA | 5-0 | 27-09-11 | D01253C | | 10 | | | | GDX0003 | D.. | 2 | | ALL |
| 067 | 16 | | PA | 5-0 | 27-09-11 | D01253C | | 9 | | | | GDX0003 | D.. | 2 | | ALL |
| 068 | 16 | | PA | 5-0 | 27-09-11 | D01253C | | 11 | | | | GDX0003 | A.. | 2 | | ALL |
| 069 | 22 | | PA | 4-0 | 27-09-12 | D04357J | | 2 | | | | TB0101H | 155 | 2 | | ALL |
| 070 | 22 | | PA | 5-0 | 27-09-12 | D00825B | | D10 | | | | TB0101H | 155 | 2 | | ALL |
| 071 | 22 | | PA | 5-0 | 27-09-12 | D00827A | | D01 | | | | TB0101H | 155 | 2 | | ALL |
| 072 | 22 | | PA | 4-0 | 27-09-12 | D00829B | | D02 | | | | TB0101H | 155 | 2 | | ALL |
| 073 | 22 | | PA | 4-0 | 27-09-12 | D00665B | | K12 | | | | TB0101H | 155 | 2 | | ALL |
| 074 | 22 | | PA | 4-0 | 27-09-12 | D01259B | | C14 | | | | TB0101H | 155 | 2 | | ALL |
| 075 | 22 | | PA | 4-0 | 27-09-13 | D05323J | | 7 | | | | TB0101H | 151 | 2 | | ALL |
| 076 | 22 | | PA | 4-0 | 27-09-13 | D05323J | | 8 | | | | TB0101H | 153 | 2 | | ALL |
| 077 | 22 | | PA | 4-0 | 27-09-13 | D01259B | | B12 | | | | TB0101H | 151 | 2 | | ALL |
| 078 | 22 | | PA | 4-0 | 27-09-13 | D01259B | | A12 | | | | TB0101H | 153 | 2 | | ALL |
| 079 | 22 | | PA | 4-0 | 27-09-13 | D04357J | | 18 | | | | TB0101H | 151 | 2 | | ALL |
| 080 | 22 | | PA | 4-0 | 27-09-13 | D04357J | | 17 | | | | TB0101H | 153 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 2

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0121 | 286T0121 | | | E1-1 SHELF (continued) | | | | | | | | | | | |
| 081 | 22 | | PA | | 5-0 | 27-09-13 | D00827A | | K13 | | TB0101H | 153 | 2 | | ALL |
| 082 | 22 | | PA | | 5-0 | 27-09-13 | D00827A | | J13 | | TB0101H | 151 | 2 | | ALL |
| 083 | 22 | | PA | | 4-0 | 27-61-11 | D04357J | | 16 | | TB0101H | 148 | 2 | | ALL |
| 084 | 22 | | PA | | 4-0 | 27-61-11 | D05323J | | 15 | | TB0101H | 148 | 2 | | ALL |
| 085 | 22 | | PA | | 5-0 | 27-61-11 | D00829B | | E02 | | TB0101H | 148 | 2 | | ALL |
| 086 | 22 | | PA | | 5-0 | 27-61-11 | D00827A | | E01 | | TB0101H | 148 | 2 | | ALL |
| 087 | 22 | | PA | | 5-0 | 27-61-11 | D00825B | | E10 | | TB0101H | 148 | 2 | | ALL |
| 088 | 22 | | PA | | 4-0 | 27-21-12 | D01263B | | B15 | | GDX0004 | D.. | 2 | | ALL |
| 089 | 22 | | PA | | 6-0 | 27-61-15 | D00827A | | E11 | | D01251B | K01 | | | ALL |
| 090 | 16 | | PA | | 4-0 | 27-61-15 | D00827C | | 3 | | GDX0004 | D.. | 2 | | ALL |
| 091 | 22 | | PA | | 6-0 | 27-61-15 | D00827A | | E12 | | D01253B | K01 | | | ALL |
| 094 | 22 | | PA | | 4-0 | 22-21-11 | TB0101G | | 51 | 2 | D04357J | 22 | | | ALL |
| 095 | 22 | | PA | | 4-0 | 22-24-11 | D05323J | | 5 | | TB0101G | 157 | 2 | | ALL |
| 096 | 22 | | PA | | 4-0 | 22-24-11 | D04357J | | 15 | | TB0101G | 157 | 2 | | ALL |
| 097 | 22 | | PA | | 4-0 | 22-24-11 | D00665B | | H15 | | TB0101G | 157 | 2 | | ALL |
| 099 | 22 | | PA | | 4-0 | 27-41-11 | D00665B | | H08 | | GDX0009 | D.. | 2 | | ALL |
| 100 | 22 | | PA | | 4-0 | 27-41-11 | D00665B | | E11 | | GDX0011 | D.. | 2 | | 150-199, 275-299 |
| 102 | 22 | | PA | | 4-0 | 27-41-11 | D00665B | | H10 | | GDX0009 | D.. | 2 | | ALL |
| 103 | 22 | | PA | | 4-0 | 27-41-11 | D00665B | | H12 | | GDX0009 | D.. | 2 | | 050-099 |
| 108 | 16 | | PA | | 4-0 | 27-41-11 | D00665C | | 3 | | GDX0009 | D.. | 2 | | ALL |
| 109 | 16 | | PA | | 4-0 | 27-41-11 | D00665C | | 2 | | GDX0009 | D.. | 2 | | ALL |
| 110 | 16 | | PA | | 4-0 | 27-41-11 | D00665C | | 11 | | GDX0009 | D.. | 2 | | ALL |
| 111 | 16 | | PA | | 4-0 | 27-41-11 | D00665C | | 8 | | GDX0009 | D.. | 2 | | ALL |
| 112 | 16 | | PA | | 4-0 | 27-41-11 | D00665C | | 7 | | GDX0009 | D.. | 2 | | ALL |
| 113 | 16 | | PA | | 4-0 | 27-41-11 | D00665C | | 10 | | GDX0009 | S.. | 2 | | ALL |
| 116 | 22 | | PA | | 4-0 | 22-22-11 | D00665A | | J12 | | D05323J | 4 | | | ALL |
| 119 | 20 | | PA | | 5-0 | 27-61-12 | D00825C | | 4 | | GDX0009 | D.. | 2 | | ALL |
| 120 | 20 | | PA | | 4-0 | 22-21-11 | D01259C | | 1 | | GDX0004 | S.. | 2 | | ALL |
| 121 | 16 | | PA | | 4-0 | 22-21-11 | D01259C | | 2 | | GDX0004 | D.. | 2 | | ALL |
| 122 | 16 | | PA | | 4-0 | 22-21-11 | D01259C | | 3 | | GDX0004 | D.. | 2 | | ALL |
| 123 | 20 | | PA | | 4-0 | 22-21-11 | D01259C | | 4 | | GDX0004 | S.. | 2 | | ALL |
| 124 | 20 | | PA | | 4-0 | 22-21-11 | D01259C | | 6 | | GDX0004 | S.. | 2 | | ALL |
| 125 | 16 | | PA | | 4-0 | 22-21-11 | D01259C | | 8 | | GDX0004 | S.. | 2 | | ALL |
| 126 | 16 | | PA | | 4-0 | 22-21-11 | D01259C | | 9 | | GDX0004 | D.. | 2 | | ALL |
| 127 | 16 | | PA | | 4-0 | 22-21-11 | D01259C | | 10 | | GDX0004 | D.. | 2 | | ALL |
| 128 | 16 | | PA | | 4-0 | 27-61-14 | D00825C | | 2 | | GDX0004 | D.. | 2 | | ALL |
| 129 | 16 | | PA | | 4-0 | 27-61-14 | D00825C | | 7 | | GDX0004 | D.. | 2 | | ALL |
| 130 | 20 | | PA | | 4-0 | 27-61-14 | D00825C | | 6 | | GDX0004 | D.. | 2 | | ALL |
| 133 | 22 | | PA | | 5-0 | 27-61-16 | D01253B | | C05 | | TB0101H | 146 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0120
 Page 3
 Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0121 | 286T0121 | | | E1-1 SHELF (continued) | | | | | | | | | | | | |
| 134 | 22 | | PA | 4-0 | 27-41-11 | D00665B | E10 | | | | GDX0011 | D.. | 2 | | 150-199, 275-299 | |
| 138 | 22 | | PA | 2-0 | 27-61-14 | D00825B | D14 | | | | D00825B | D15 | | | ALL | |
| 139 | 22 | | PA | 2-0 | 27-61-14 | D00825B | B14 | | | | D00825B | B15 | | | ALL | |
| 140 | 20 | | PA | 3-0 | 27-61-15 | D00827C | 6 | | | | GDX0006 | D.. | 2 | | ALL | |
| 144 | 22 | | PA | 2-0 | 27-61-15 | D00827A | D05 | | | | D00827A | D06 | | | ALL | |
| 145 | 22 | | PA | 2-0 | 27-61-15 | D00827A | B05 | | | | D00827A | B06 | | | ALL | |
| 146 | 16 | | PA | 4-0 | 27-61-16 | D00829C | 8 | | | | GDX0005 | D.. | 2 | | ALL | |
| 147 | 16 | | PA | 4-0 | 27-61-16 | D00829C | 3 | | | | GDX0005 | D.. | 2 | | ALL | |
| 148 | 16 | | PA | 4-0 | 27-61-16 | D00829C | 2 | | | | GDX0005 | D.. | 2 | | ALL | |
| 149 | 16 | | PA | 4-0 | 27-61-16 | D00829C | 7 | | | | GDX0005 | D.. | 2 | | ALL | |
| 150 | 16 | | PA | 4-0 | 27-61-16 | D00829C | 9 | | | | GDX0005 | S.. | 2 | | ALL | |
| 154 | 22 | | PA | 2-0 | 27-61-16 | D00829B | D06 | | | | D00829B | D07 | | | ALL | |
| 155 | 22 | | PA | 2-0 | 27-61-16 | D00829B | B06 | | | | D00829B | B07 | | | ALL | |
| 157 | 20 | | PA | 5-0 | 27-61-14 | D00825C | 5 | | | | GDX0009 | D.. | 2 | | ALL | |
| 159 | 20 | | PA | 5-0 | 27-61-15 | D00827C | 5 | | | | GDX0008 | D.. | 2 | | ALL | |
| 160 | 22 | | PA | 2-0 | 27-61-16 | D00829B | D03 | | | | D00829B | C03 | | | ALL | |
| 161 | 20 | | PA | 5-0 | 27-61-16 | D00829C | 5 | | | | GDX0005 | D.. | 2 | | ALL | |
| 162 | 22 | | PA | 4-0 | 27-41-11 | D00665B | E12 | | | | GDX0011 | D.. | 2 | | 150-199, 275-299 | |
| 163 | 22 | | PQ | GM | 5-0 | 27-41-31 | D05135J | 11 | | | TB0101G | 102 | 2 | | 050-099, 155-199, 275-299 | |
| 163Z | | | | GM | 0-0 | 27-41-31 | D05135J | DED | | | TB0101G | DED | | | 050-099, 155-199, 275-299 | |
| 170 | 22 | | PA | 4-0 | 27-41-11 | D00665B | G08 | | | | GDX0011 | D.. | 2 | | ALL | |
| 171 | 22 | | PA | 4-0 | 27-41-11 | D00665B | G09 | | | | GDX0011 | D.. | 2 | | ALL | |
| 172 | 22 | | PA | 4-0 | 27-41-11 | D00665B | G10 | | | | GDX0011 | D.. | 2 | | ALL | |
| 173 | 22 | | PA | 4-0 | 27-41-11 | D00665B | G11 | | | | GDX0011 | D.. | 2 | | ALL | |
| 174 | 22 | | PA | 4-0 | 27-41-11 | D00665B | G12 | | | | GDX0011 | D.. | 2 | | ALL | |
| 175 | 22 | | PA | 4-0 | 27-41-11 | D00665B | G13 | | | | GDX0011 | D.. | 2 | | ALL | |
| 176 | 22 | | PA | 4-0 | 27-41-11 | D00665B | G14 | | | | GDX0011 | D.. | 2 | | ALL | |
| 177 | 22 | | PA | 4-0 | 27-41-11 | D00665B | G15 | | | | GDX0011 | D.. | 2 | | ALL | |
| 178 | 22 | | PA | 4-0 | 27-61-14 | D00825B | H12 | | | | D04357J | 23 | | | ALL | |
| 179 | 20 | | PA | 4-0 | 27-61-14 | GDX0006 | D.. | 2 | | | D04357J | 24 | | | ALL | |
| 180 | 22 | | PA | 4-0 | 27-61-16 | D00829B | C02 | | | | D00665B | J12 | | | ALL | |
| 181 | 22 | | PA | 4-0 | 27-41-11 | D00665B | H11 | | | | GDX0009 | D.. | 2 | | ALL | |
| 196 | 16 | | PA | 4-0 | 27-11-12 | D00665C | 9 | | | | R00024 | = B | \$ | | ALL | |
| 197 | 16 | | PA | 2-0 | 27-11-12 | GDX0010 | D.. | 2 | | | R00024 | = A | \$ | | ALL | |
| 201B | 22 | | PB | IA | 5-0 | 27-61-14 | D00825B | J15 | | | TB0101H | 146 | 2 | | ALL | |
| 201R | 22 | | PB | IA | 0-0 | 27-61-14 | D00825B | K15 | | | TB0101H | 144 | 2 | | ALL | |
| 202B | 22 | | PB | IB | 5-0 | 27-61-15 | D00827A | G08 | | | D05405J | 3 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 4

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0121 | 286T0121 | | | E1-1 SHELF (continued) | | | | | | | | | | | |
| 202R | 22 | PB | IB | | 0-0 | 27-61-15 | D00827A | G09 | | | D05405J | 1 | | | ALL |
| 203B | 22 | PB | IC | | 4-0 | 27-61-15 | D00827A | J11 | | | TB0101G | 143 | 2 | | ALL |
| 203R | 22 | PB | IC | | 0-0 | 27-61-15 | D00827A | K11 | | | TB0101G | 142 | 2 | | ALL |
| 204B | 22 | PB | ID | | 5-0 | 27-61-15 | D00827A | G11 | | | D05405J | 11 | | | ALL |
| 204R | 22 | PB | ID | | 0-0 | 27-61-15 | D00827A | G10 | | | D05405J | 10 | | | ALL |
| 205B | 22 | PB | IE | | 4-0 | 27-61-15 | D05405J | 9 | | | TB0101G | 143 | 2 | | ALL |
| 205R | 22 | PB | IE | | 0-0 | 27-61-15 | D05405J | 8 | | | TB0101G | 142 | 2 | | ALL |
| 206B | 22 | PB | IF | | 4-0 | 27-61-15 | D05405J | 15 | | | TB0101G | 143 | 2 | | ALL |
| 206R | 22 | PB | IF | | 0-0 | 27-61-15 | D05405J | 14 | | | TB0101G | 142 | 2 | | ALL |
| 207B | 22 | PB | IG | | 5-0 | 27-61-15 | D00827A | J06 | | | TB0101H | 146 | 2 | | ALL |
| 207R | 22 | PB | IG | | 0-0 | 27-61-15 | D00827A | K06 | | | TB0101H | 144 | 2 | | ALL |
| 208B | 22 | PB | IH | | 4-0 | 27-61-16 | D05135J | 9 | | | TB0101H | 146 | 2 | | ALL |
| 208R | 22 | PB | IH | | 0-0 | 27-61-16 | D05135J | 8 | | | TB0101H | 144 | 2 | | ALL |
| 209B | 22 | PB | II | | 4-0 | 27-61-16 | D05135J | 2 | | | TB0101H | 146 | 2 | | ALL |
| 209R | 22 | PB | II | | 0-0 | 27-61-16 | D05135J | 1 | | | TB0101H | 144 | 2 | | ALL |
| 210B | 22 | PB | IJ | | 6-0 | 27-61-16 | D01251B | C05 | | | TB0101H | 146 | 2 | | ALL |
| 210R | 22 | PB | IJ | | 0-0 | 27-61-16 | D01251B | A05 | | | TB0101H | 144 | 2 | | ALL |
| 211B | 22 | PB | IK | | 5-0 | 27-61-16 | D00829B | J07 | | | TB0101H | 146 | 2 | | ALL |
| 211R | 22 | PB | IK | | 0-0 | 27-61-16 | D00829B | K07 | | | TB0101H | 144 | 2 | | ALL |
| 212 | 20 | UA | | | 0-18 | 22-21-11 | D04357J | | | FD | GD0007 | S.. | 2 | | ALL |
| 212B | 24 | PW | IL | | 4-0 | 22-21-11 | D04357J | 21 | | | TB0101G | 50 | 2 | | ALL |
| 212R | 24 | PW | IL | | 0-0 | 22-21-11 | D04357J | 20 | | | TB0101G | 49 | 2 | | ALL |
| 212Z | | | IL | | 0-0 | 22-21-11 | D04357J | | | FD | TB0101G | | | FA | ALL |
| 214B | 24 | PW | IN | | 4-0 | 22-21-11 | D01259B | A15 | | | TB0101G | 50 | 2 | | ALL |
| 214R | 24 | PW | IN | | 0-0 | 22-21-11 | D01259B | A14 | | | TB0101G | 49 | 2 | | ALL |
| 214Z | | | IN | | 0-0 | 22-21-11 | D01259B | DED | | | TB0101G | | | FA | ALL |
| 215 | 20 | UA | | | 0-18 | 22-21-11 | D05323J | | | FE | GD0010 | S.. | 2 | | ALL |
| 215B | 24 | PW | IO | | 4-0 | 22-21-11 | D05323J | 10 | | | TB0101G | 50 | 2 | | ALL |
| 215R | 24 | PW | IO | | 0-0 | 22-21-11 | D05323J | 9 | | | TB0101G | 49 | 2 | | ALL |
| 215Z | | | IO | | 0-0 | 22-21-11 | D05323J | | | FE | TB0101G | | | FA | ALL |
| 216B | 24 | PW | IP | | 5-0 | 22-22-11 | D00665B | K15 | | | TB0101G | 53 | 2 | | ALL |
| 216R | 24 | PW | IP | | 0-0 | 22-22-11 | D00665B | K14 | | | TB0101G | 52 | 2 | | ALL |
| 216Z | | | IP | | 0-0 | 22-22-11 | D00665B | DED | | | TB0101G | | | FB | ALL |
| 217 | 20 | UA | | | 0-18 | 22-22-11 | D04357J | | | FF | GD0007 | S.. | 2 | | ALL |
| 217B | 24 | PW | IQ | | 4-0 | 22-22-11 | D04357J | 4 | | | TB0101G | 53 | 2 | | ALL |
| 217R | 24 | PW | IQ | | 0-0 | 22-22-11 | D04357J | 3 | | | TB0101G | 52 | 2 | | ALL |
| 217Z | | | IQ | | 0-0 | 22-22-11 | D04357J | | | FF | TB0101G | | | FB | ALL |
| 218 | 20 | UA | | | 0-18 | 22-22-11 | D05323J | | | FG | GD0010 | S.. | 2 | | ALL |
| 218B | 24 | PW | IR | | 4-0 | 22-22-11 | D05323J | 20 | | | TB0101G | 53 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 5

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------|----------|-------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0121 | 286T0121 | | | E1-1 SHELF (continued) | | | | | | | | | | | | |
| 218R | 24 | PW | IR | 0-0 | 22-22-11 | | D05323J | 19 | | | | TB0101G | 52 | 2 | | ALL |
| 218Z | | | IR | 0-0 | 22-22-11 | | D05323J | | | FG | | TB0101G | | | FB | ALL |
| 241B | 24 | PW | JP | 5-0 | 32-45-13 | | D04357J | 25 | | | | D06756P | 1 | | | 050-099 |
| 241B | 24 | PW | JP | 6-0 | 32-45-13 | | D04357J | 25 | | | | D06756P | 1 | | | 150-199 |
| 241R | 24 | PW | JP | 0-0 | 32-45-13 | | D04357J | 26 | | | | D06756P | 2 | | | 050-099, 150-199 |
| 241Z | | | JP | 0-0 | 32-45-13 | | D04357J | 6 | | | | D06756P | 3 | | | 050-099, 150-199 |
| 242B | 24 | PW | JQ | 5-0 | 32-45-13 | | D04357J | 27 | | | | D06756P | 4 | | | 050-099, 150-199 |
| 242R | 24 | PW | JQ | 0-0 | 32-45-13 | | D04357J | 28 | | | | D06756P | 5 | | | 050-099, 150-199 |
| 242Z | | | JQ | 0-0 | 32-45-13 | | D04357J | 13 | | | | D06756P | 6 | | | 050-099, 150-199 |
| 243B | 24 | PW | JR | 5-0 | 32-45-13 | | D04357J | 29 | | | | D06756P | 7 | | | 050-099, 150-199 |
| 243R | 24 | PW | JR | 0-0 | 32-45-13 | | D04357J | 30 | | | | D06756P | 8 | | | 050-099, 150-199 |
| 243Z | | | JR | 0-0 | 32-45-13 | | D04357J | 31 | | | | D06756P | 9 | | | 050-099, 150-199 |
| 244B | 24 | PW | JS | 5-0 | 32-45-13 | | D04357J | 32 | | | | D06756P | 10 | | | 050-099, 150-199 |
| 244R | 24 | PW | JS | 0-0 | 32-45-13 | | D04357J | 33 | | | | D06756P | 11 | | | 050-099, 150-199 |
| 244Z | | | JS | 0-0 | 32-45-13 | | D04357J | 34 | | | | D06756P | 12 | | | 050-099, 150-199 |
| 301B | 22 | PC | MA | 5-0 | 27-61-14 | | D00825B | J14 | | | | TB0101G | 44 | 2 | | ALL |
| 301R | 22 | PC | MA | 0-0 | 27-61-14 | | D00825B | J12 | | | | TB0101G | 43 | 2 | | ALL |
| 301Y | 22 | PC | MA | 0-0 | 27-61-14 | | D00825B | J13 | | | | TB0101G | 45 | 2 | | ALL |
| 302B | 22 | PC | MB | 5-0 | 27-61-14 | | D00825B | K14 | | | | TB0101G | 47 | 2 | | ALL |
| 302R | 22 | PC | MB | 0-0 | 27-61-14 | | D00825B | K12 | | | | TB0101G | 46 | 2 | | ALL |
| 302Y | 22 | PC | MB | 0-0 | 27-61-14 | | D00825B | K13 | | | | TB0101G | 48 | 2 | | ALL |
| 303B | 22 | PC | MC | 5-0 | 27-61-15 | | D00827A | J05 | | | | TB0101G | 44 | 2 | | ALL |
| 303R | 22 | PC | MC | 0-0 | 27-61-15 | | D00827A | J03 | | | | TB0101G | 43 | 2 | | ALL |
| 303Y | 22 | PC | MC | 0-0 | 27-61-15 | | D00827A | J04 | | | | TB0101G | 45 | 2 | | ALL |
| 304B | 22 | PC | MD | 5-0 | 27-61-15 | | D00827A | K05 | | | | TB0101G | 47 | 2 | | ALL |
| 304R | 22 | PC | MD | 0-0 | 27-61-15 | | D00827A | K03 | | | | TB0101G | 46 | 2 | | ALL |
| 304Y | 22 | PC | MD | 0-0 | 27-61-15 | | D00827A | K04 | | | | TB0101G | 48 | 2 | | ALL |
| 305B | 22 | PC | ME | 5-0 | 27-61-15 | | D00827A | K10 | | | | D05405J | 6 | | | ALL |
| 305R | 22 | PC | ME | 0-0 | 27-61-15 | | D00827A | K08 | | | | D05405J | 5 | | | ALL |
| 305Y | 22 | PC | ME | 0-0 | 27-61-15 | | D00827A | K09 | | | | D05405J | 7 | | | ALL |
| 306B | 22 | PC | MF | 5-0 | 27-61-15 | | D00827A | J10 | | | | D05405J | 16 | | | ALL |
| 306R | 22 | PC | MF | 0-0 | 27-61-15 | | D00827A | J08 | | | | D05405J | 12 | | | ALL |
| 306Y | 22 | PC | MF | 0-0 | 27-61-15 | | D00827A | J09 | | | | D05405J | 13 | | | ALL |
| 307B | 22 | PC | MG | 4-0 | 27-61-16 | | D05135J | 4 | | | | TB0101G | 44 | 2 | | ALL |
| 307R | 22 | PC | MG | 0-0 | 27-61-16 | | D05135J | 6 | | | | TB0101G | 43 | 2 | | ALL |
| 307Y | 22 | PC | MG | 0-0 | 27-61-16 | | D05135J | 7 | | | | TB0101G | 45 | 2 | | ALL |
| 308B | 22 | PC | MH | 4-0 | 27-61-16 | | D05135J | 10 | | | | TB0101G | 47 | 2 | | ALL |
| 308R | 22 | PC | MH | 0-0 | 27-61-16 | | D05135J | 3 | | | | TB0101G | 46 | 2 | | ALL |
| 308Y | 22 | PC | MH | 0-0 | 27-61-16 | | D05135J | 5 | | | | TB0101G | 48 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 6

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------------------------|-------|-------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0121 | 286T0121 | E1-1 SHELF (continued) | | | | | | | | | | | | | |
| 309B | 22 | PC | MI | 5-0 | 27-61-16 | D00829B | | J06 | | | TB0101G | 44 | 2 | | ALL |
| 309R | 22 | PC | MI | 0-0 | 27-61-16 | D00829B | | J04 | | | TB0101G | 43 | 2 | | ALL |
| 309Y | 22 | PC | MI | 0-0 | 27-61-16 | D00829B | | J05 | | | TB0101G | 45 | 2 | | ALL |
| 310B | 22 | PC | MJ | 5-0 | 27-61-16 | D00829B | | K06 | | | TB0101G | 47 | 2 | | ALL |
| 310R | 22 | PC | MJ | 0-0 | 27-61-16 | D00829B | | K04 | | | TB0101G | 46 | 2 | | ALL |
| 310Y | 22 | PC | MJ | 0-0 | 27-61-16 | D00829B | | K05 | | | TB0101G | 48 | 2 | | ALL |
| FRD | | | | 0-0 | 22-21-11 | D04357J | | 19 | | | D04357J | | | | FD ALL |
| FRE | | | | 0-0 | 22-21-11 | D05323J | | 11 | | | D05323J | | | | FE ALL |
| FRF | | | | 0-0 | 22-22-11 | D04357J | | 5 | | | D04357J | | | | FF ALL |
| FRG | | | | 0-0 | 22-22-11 | D05323J | | 21 | | | D05323J | | | | FG ALL |
| W0122 | 286T0122 | AFT MID CABIN MOD | | | | | | | | | | | | | |
| 009 | 22 | PA | | 5-0 | 23-42-11 | D06482P | | 1 | | | L00406 | = P | \$ | | 150-199 |
| 010 | 20 | PA | | 5-0 | 23-42-11 | D06482P | | 4 | | | L00406 | = G | \$ | | 150-199 |
| 013 | 22 | PA | | 5-0 | 33-25-11 | D06482P | | 2 | | | B00145 | HI | C | * | 150-199 |
| 014 | 22 | PA | | 5-0 | 33-25-11 | D06482P | | 6 | | | L00408 | = P | \$ | | 150-199 |
| 042 | 18 | PA | | 4-0 | 33-22-31 | D06028P | | 2 | DL | | L00192 | = P | C | | 150-199 |
| 043 | 18 | PA | | 4-0 | 33-22-31 | D06028P | | 3 | DL | | L00192 | = G | C | * | 150-199 |
| 044 | 18 | PA | | 5-0 | 33-22-31 | L00193 | | = G | C | | L00192 | = G | C | * | 150-199 |
| 045 | 18 | PA | | 4-0 | 33-22-31 | L00193 | | = P | C | | D06028P | 4 | DL | | 150-199 |
| 046 | 20 | PA | | 5-0 | 33-22-42 | D06028P | | 5 | | | L00420 | = G | C | * | 150-199 |
| 047 | 20 | PA | | 5-0 | 33-22-42 | D06028P | | 1 | | | L00420 | = P | C | * | 150-199 |
| 048 | 22 | PA | | 7-0 | 33-22-42 | L00419 | | = P | C | | L00420 | = P | C | * | 150-199 |
| 049 | 22 | PA | | 7-0 | 33-22-42 | L00419 | | = G | C | | L00420 | = G | C | * | 150-199 |
| 112 | 24 | PK | | 5-0 | 23-42-12 | D06482P | | 12 | | | B00145 | H/L | C | | 150-199 |
| 113 | 22 | PQ | EM | 5-0 | 23-42-12 | D06482P | | 13 | | | B00145 | 28V | C | | 150-199 |
| 113Z | | | EM | 0-0 | 23-42-12 | D06482P | | DED | | | B00145 | DED | | | 150-199 |
| 114 | 20 | PA | | 5-0 | 23-42-12 | D06482P | | 14 | | | B00145 | GRD | C | | 150-199 |
| 116 | 24 | PK | | 5-0 | 23-42-12 | D06482P | | 16 | | | B00146 | H/L | C | | 150-199 |
| 117 | 22 | PQ | EQ | 5-0 | 23-42-12 | D06482P | | 17 | | | B00146 | 28V | C | | 150-199 |
| 117Z | | | EQ | 0-0 | 23-42-12 | D06482P | | DED | | | B00146 | DED | | | 150-199 |
| 118 | 20 | PA | | 5-0 | 23-42-12 | D06482P | | 18 | | | B00146 | GRD | C | | 150-199 |
| 119 | 24 | PK | | 5-0 | 23-34-13 | D06482P | | 19 | | | B00145 | HI | C | * | 150-199 |
| 120 | 24 | PK | | 5-0 | 23-34-13 | D06482P | | 20 | | | B00146 | HI | C | * | 150-199 |
| 121 | 18 | PA | | 7-0 | 33-51-12 | D06650P | | 1 | DL | | L00321 | 1 | C | | 150-154, 156, 162-199 |
| 121 | 18 | PA | | 8-0 | 33-51-12 | D06650P | | 1 | DL | | ST0935R | REF | * | | 155 |
| 121 | 18 | PA | | 7-0 | 33-51-12 | D06650P | | 1 | DL | | L01075 | 1 | C | | 157 |
| 122 | 18 | PA | | 7-0 | 33-51-12 | D06650P | | 2 | DL | | L00321 | 2 | C | | 150-154, 156, 162-199 |
| 122 | 18 | PA | | 8-0 | 33-51-12 | D06650P | | 2 | DL | | ST0935R | REF | * | | 155 |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 7

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------|----|--------------------------------------|-------------|----------|---------|------|------|--------|-------|---------|------|--------|------------------------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0122 | 286T0122 | | | AFT MID CABIN MOD (continued) | | | | | | | | | | | | |
| 122 | 18 | | PA | | 7-0 | 33-51-12 | D06650P | | 2 | DL | | L01075 | 2 | C | 157 | |
| 123 | 22 | | PA | | 4-0 | 23-34-13 | D06482P | | 23 | | | L00409 | = P | \$ | 150-199 | |
| 124 | 22 | | PA | | 5-0 | 23-34-13 | D06482P | | 24 | | | L00410 | = P | \$ | 150-199 | |
| 128 | 22 | | PA | | 5-0 | 33-25-11 | D06482P | | 3 | | | B00146 | HI | C | * 150-199 | |
| 129 | 22 | | PA | | 5-0 | 33-25-11 | D06482P | | 5 | | | L00407 | = P | \$ | 150-199 | |
| 131 | 20 | | PA | | 5-0 | 33-51-13 | D06652P | | 1 | | | L00655 | 1 | C | 150-154, 156, 162-199 | |
| 131 | 20 | | PA | | 7-0 | 33-51-13 | D06652P | | 1 | | | ST0935L | REF | * | 155 | |
| 131 | 20 | | PA | | 6-0 | 33-51-13 | D06652P | | 1 | | | L01074 | 1 | C | 157 | |
| 132 | 20 | | PA | | 5-0 | 33-51-13 | D06652P | | 2 | | | L00655 | 2 | C | 150-154, 156, 162-199 | |
| 132 | 20 | | PA | | 7-0 | 33-51-13 | D06652P | | 2 | | | ST0935L | REF | * | 155 | |
| 132 | 20 | | PA | | 6-0 | 33-51-13 | D06652P | | 2 | | | L01074 | 2 | C | 157 | |
| 206B | 22 | | PB | IF | 6-0 | 23-31-14 | D06482P | | 8 | | | B00243 | COM | Z | 150-199 | |
| 206R | 22 | | PB | IF | 0-0 | 23-31-14 | D06482P | | 7 | | | B00243 | 4K | Z | 150-199 | |
| W0123 | 286T0123 | | | FWD CABIN MID (R) | | | | | | | | | | | | |
| 030 | 20 | | PA | | 5-0 | 33-27-11 | SP00439 | | | 9 | | D13553 | 10 | | 050-099, 150-199 | |
| 031 | 20 | | PA | | 5-0 | 33-27-11 | SP00441 | | | 9 | | D13553 | 9 | | 050-099, 150-199 | |
| 032 | 20 | | PA | | 5-0 | 33-27-11 | D13553 | | 8 | | | D06738P | 2 | | 050-099, 150-199 | |
| 033 | 20 | | PA | | 5-0 | 33-27-11 | D13553 | | 7 | | | D06738P | 3 | | 050-099, 150-154, 157-165, 167-199 | |
| 033 | 20 | | PQ | BH | 5-0 | 33-27-11 | D13553 | | 7 | | | D06738P | 3 | | 155-156, 166 | |
| 033Z | | | | BH | 0-0 | 33-27-11 | D13553 | DED | | | | D06738P | DED | | 155-156, 166 | |
| 034 | 20 | | PA | | 5-0 | 33-27-11 | D06738P | | 1 | | | D13553 | 5 | | 050-099, 150-154, 157-165, 167-199 | |
| 034 | 20 | | PQ | BI | 5-0 | 33-27-11 | D06738P | | 1 | | | D13553 | 5 | | 155-156, 166 | |
| 034Z | | | | BI | 0-0 | 33-27-11 | D06738P | DED | | | | D13553 | DED | | 155-156, 166 | |
| 035 | 20 | | PA | | 7-0 | 33-27-11 | L01108 | = G | | E | * | D06738P | 4 | | 050-099, 150-199 | |
| 039 | 20 | | PA | | 5-0 | 33-27-11 | SP00445 | | | 9 | | D13553 | 12 | | 050-099, 150-199 | |
| 040 | 20 | | PA | | 5-0 | 33-27-11 | SP00447 | | | 9 | | D13553 | 11 | | 050-099, 150-199 | |
| 041 | 20 | | PA | | 5-0 | 33-27-11 | D06738P | | 5 | | | D13554 | 5 | | 050-099, 150-154, 157-165, 167-199 | |
| 041 | 20 | | PQ | BP | 5-0 | 33-27-11 | D06738P | | 5 | | | D13554 | 5 | | 155-156, 166 | |
| 041Z | | | | BP | 0-0 | 33-27-11 | D06738P | DED | | | | D13554 | DED | | 155-156, 166 | |
| 042 | 20 | | PA | | 5-0 | 33-27-11 | D13554 | | 9 | | | SP00449 | 9 | | 050-099, 150-199 | |
| 043 | 20 | | PA | | 5-0 | 33-27-11 | D13554 | | 10 | | | SP00451 | 9 | | 050-099, 150-199 | |
| 044 | 20 | | PA | | 5-0 | 33-27-11 | D13554 | | 8 | | | D06738P | 6 | | 050-099, 150-199 | |
| 047 | 20 | | PA | | 5-0 | 33-27-11 | D13554 | | 12 | | | SP00453 | 9 | | 050-099, 150-199 | |
| 048 | 20 | | PA | | 5-0 | 33-27-11 | D13554 | | 11 | | | SP00455 | 9 | | 050-099, 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 8

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0123 | 286T0123 | | | FWD CABIN MID (R) (continued) | | | | | | | | | | | |
| 049 | 20 | | PA | | 5-0 | 33-27-11 | D13554 | | | | D06738P | | 7 | | 050-099, 150-154, 157-165, 167-199 |
| 049 | 20 | | PQ | BX | 5-0 | 33-27-11 | D13554 | | | | D06738P | | 7 | | 155-156, 166 |
| 049Z | | | | BX | 0-0 | 33-27-11 | D13554 | DED | | | D06738P | DED | | | 155-156, 166 |
| 054 | 20 | | PA | | 7-0 | 33-27-11 | D06738P | | | 8 | L01108 | =G | E | * | 050-099, 150-199 |
| A-A | | | | | 0-0 | 33-27-11 | SP00439 | | | 9 | L01108 | BLK | | | 050-099, 150-199 |
| A-B | | | | | 0-0 | 33-27-11 | SP00441 | | | 9 | L01108 | BLK | | | 050-099, 150-199 |
| A-C | | | | | 0-0 | 33-27-11 | SP00445 | | | 9 | L01108 | WHT | | | 050-099, 150-199 |
| A-D | | | | | 0-0 | 33-27-11 | SP00447 | | | 9 | L01108 | WHT | | | 050-099, 150-199 |
| A-G | | | | | 0-0 | 33-27-11 | L01109 | WHT | | | SP00455 | | 9 | | 050-099, 150-199 |
| A-H | | | | | 0-0 | 33-27-11 | L01109 | WHT | | | SP00453 | | 9 | | 050-099, 150-199 |
| A-I | | | | | 0-0 | 33-27-11 | L01109 | BLK | | | SP00449 | | 9 | | 050-099, 150-199 |
| A-J | | | | | 0-0 | 33-27-11 | L01109 | BLK | | | SP00451 | | 9 | | 050-099, 150-199 |
| W0124 | 286T0124 | | | MID-CABIN LOWERED CEILING | | | | | | | | | | | |
| 005 | 22 | | PA | | 5-0 | 33-27-11 | D11402 | | | 5 | D00192 | | 5 | | 162-199 |
| 007 | 22 | | PA | | 5-0 | 33-27-11 | D11402 | | | 7 | D00192 | | 7 | | 162-199 |
| 008 | 22 | | PA | | 4-0 | 33-27-11 | D11402 | | | 8 | L00839 | =G | E | * | 162-199 |
| 009 | 22 | | PA | | 5-0 | 33-27-11 | D11402 | | | 9 | D00192 | | 9 | | 162-199 |
| 010 | 22 | | PA | | 5-0 | 33-27-11 | D11402 | | | 10 | D00192 | | 10 | | 162-199 |
| 011 | 22 | | PA | | 4-0 | 33-27-11 | D11402 | | | 11 | SP03046 | | 9 | | 162-199 |
| 012 | 22 | | PA | | 4-0 | 33-27-11 | D11402 | | | 12 | SP03044 | | 9 | | 162-199 |
| 018 | 22 | | PA | | 4-0 | 33-27-11 | D00192 | | | 8 | L00839 | =G | E | * | 162-199 |
| 021 | 22 | | PA | | 4-0 | 33-27-11 | D00192 | | | 11 | SP03046 | | 9 | | 162-199 |
| 022 | 22 | | PA | | 4-0 | 33-27-11 | D00192 | | | 12 | SP03044 | | 9 | | 162-199 |
| A-A | | | | | 0-0 | 33-27-11 | L00839 | BLK | | | D11402 | | 2 | | 162-199 |
| A-B | | | | | 0-0 | 33-27-11 | L00839 | BLK | | | D11402 | | 3 | | 162-199 |
| A-C | | | | | 0-0 | 33-27-11 | L00839 | WHT | | | SP03046 | | 9 | | 162-199 |
| A-D | | | | | 0-0 | 33-27-11 | L00839 | WHT | | | SP03044 | | 9 | | 162-199 |
| B-A | | | | | 0-0 | 33-27-11 | L00840 | BLK | | | D00192 | | 1 | | 162-199 |
| B-B | | | | | 0-0 | 33-27-11 | L00840 | BLK | | | D00192 | | 2 | | 162-199 |
| B-C | | | | | 0-0 | 33-27-11 | L00840 | WHT | | | D00192 | | 3 | | 162-199 |
| B-D | | | | | 0-0 | 33-27-11 | L00840 | WHT | | | D00192 | | 4 | | 162-199 |
| W0125 | 286T0125 | | | E1-3 SHELF, CENTER | | | | | | | | | | | |
| 001 | 22 | | PQ | AA | 3-9 | 34-12-11 | D05635J | | | 4 | D04239P | | 8 | | ALL |
| 001Z | | | | AA | 0-0 | 34-12-11 | D05635J | DED | | | D04239P | DED | | | ALL |
| 002 | 22 | | PA | | 4-0 | 34-12-11 | D05635J | | | 5 | GDY0007 | A.. | 2 | | 050-099, 277-299 |
| 002 | 22 | | PA | | 4-0 | 34-12-11 | D05635J | | | 5 | GDY0008 | A.. | 2 | | 150-199, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 9

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0125 | 286T0125 | | | E1-3 SHELF, CENTER (continued) | | | | | | | | | | | |
| 003 | 22 | PQ | AC | 2-8 | 34-12-11 | D05635J | | 6 | | | TB0105G | 139 | 2 | | ALL |
| 003Z | | | AC | 0-0 | 34-12-11 | D05635J | | DED | | | TB0105G | DED | | | ALL |
| 005 | 24 | PK | | 4-6 | 22-15-12 | D05625J | | 5 | | | TB0105F | C117 | 2 | | ALL |
| 009 | 22 | PA | | 3-0 | 22-11-12 | D05635J | | 1 | | | TB0105F | A122 | 2 | | ALL |
| 025 | 22 | PA | | 4-0 | 22-11-32 | D05625J | | 22 | | | TB0105H | 21 | 2 | | ALL |
| 057 | 24 | PK | | 2-3 | 22-14-11 | D05625J | | 25 | | | TB0105H | 188 | 2 | | ALL |
| 059 | 24 | PK | | 2-3 | 22-14-31 | D05625J | | 24 | | | TB0105H | 188 | 2 | | ALL |
| 060 | 24 | PK | | 2-3 | 22-14-31 | D05625J | | 4 | | | TB0105H | 188 | 2 | | ALL |
| 062 | 24 | PK | | 4-6 | 22-14-11 | D05625J | | 23 | | | TB0105F | A117 | 2 | | ALL |
| 074 | 24 | PK | | 3-8 | 22-15-12 | D05625J | | 10 | | | TB0105F | A135 | 2 | | ALL |
| 089 | 24 | PK | | 2-3 | 22-14-21 | D05625J | | 29 | | | TB0105H | 188 | 2 | | ALL |
| 105 | 22 | PQ | EE | 3-7 | 34-12-11 | D04239P | | 2 | | | TB0105G | 139 | 2 | | ALL |
| 105Z | | | EE | 0-0 | 34-12-11 | D04239P | | DED | | | TB0105G | DED | | | ALL |
| 106 | 22 | PQ | EF | 3-8 | 34-12-11 | D04239P | | 6 | | | TB0105H | 143 | 2 | | ALL |
| 106Z | | | EF | 0-0 | 34-12-11 | D04239P | | DED | | | TB0105H | DED | | | ALL |
| 107 | 22 | PQ | EG | 3-8 | 34-12-11 | D04239P | | 7 | | | TB0105H | 37 | 2 | | ALL |
| 107Z | | | EG | 0-0 | 34-12-11 | D04239P | | DED | | | TB0105H | DED | | | ALL |
| 202B | 24 | PL | IB | 4-9 | 27-32-11 | D05625J | | 31 | | | TB0105F | C003 | 2 | | ALL |
| 202R | 24 | PL | IB | 0-0 | 27-32-11 | D05625J | | 30 | | | TB0105F | A003 | 2 | | ALL |
| 203B | 24 | PW | 1C | 3-9 | 34-12-61 | D05625J | | 2 | | | TB0105F | C036 | 2 | | ALL |
| 203R | 24 | PW | 1C | 0-0 | 34-12-61 | D05625J | | 1 | | | TB0105F | A036 | 2 | | ALL |
| 203Z | | | 1C | 0-0 | 34-12-61 | D05625J | | 3 | | | GDY0007 | S.. | 2 | | 050-099, 277-299 |
| 203Z | | | 1C | 0-0 | 34-12-61 | D05625J | | 3 | | | GDY0006 | S.. | 2 | | 150-199, 275-276 |
| 205B | 22 | PR | IE | 2-9 | 34-12-11 | D05635J | | 3 | | | GDY0007 | A.. | 2 | | 050-099, 277-299 |
| 205B | 22 | PR | IE | 2-9 | 34-12-11 | D05635J | | 3 | | | GDY0008 | A.. | 2 | | 150-199, 275-276 |
| 205R | 22 | PR | IE | 0-0 | 34-12-11 | D05635J | | 2 | | | TB0105H | 143 | 2 | | ALL |
| 205Z | | | IE | 0-0 | 34-12-11 | D05635J | | DED | | | TB0105H | DED | | | ALL |
| 206B | 22 | PR | IF | 2-9 | 34-12-11 | D05635J | | 8 | | | GDY0007 | A.. | 2 | | 050-099, 277-299 |
| 206B | 22 | PR | IF | 2-9 | 34-12-11 | D05635J | | 8 | | | GDY0008 | A.. | 2 | | 150-199, 275-276 |
| 206R | 22 | PR | IF | 0-0 | 34-12-11 | D05635J | | 7 | | | TB0105H | 143 | 2 | | ALL |
| 206Z | | | IF | 0-0 | 34-12-11 | D05635J | | DED | | | TB0105H | DED | | | ALL |
| 231B | 24 | PW | JF | 4-6 | 22-15-11 | D05625J | | 8 | | | TB0105G | 115 | 2 | | ALL |
| 231R | 24 | PW | JF | 0-0 | 22-15-11 | D05625J | | 7 | | | TB0105G | 114 | 2 | | ALL |
| 231Z | | | JF | 0-0 | 22-15-11 | D05625J | | 9 | | | GDY0002 | S.. | 2 | | ALL |
| 555B | 24 | PW | WE | 3-9 | 34-16-11 | D05635J | | 14 | | | TB0105H | 13 | 2 | | ALL |
| 555R | 24 | PW | WE | 0-0 | 34-16-11 | D05635J | | 13 | | | TB0105H | 11 | 2 | | ALL |
| 555Z | | | WE | 0-0 | 34-16-11 | D05635J | | 12 | | | GDY0001 | S.. | 2 | | 050-099, 150-199 |
| 555Z | | | WE | 0-0 | 34-16-11 | D05635J | | 12 | | | GDY0002 | S.. | 2 | | 275-299 |
| 709 | 20 | PQ | G9 | 5-4 | 22-31-12 | D04239P | | 4 | | | TB0105G | 187 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 10

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0125 | 286T0125 | | | E1-3 SHELF, CENTER (continued) | | | | | | | | | | | |
| 709Z | | | | G9 | 0-0 | 22-31-12 | D04239P | DED | | | TB0105G | DED | | | ALL |
| W0127 | 286T0127 | | | E1-4 C,SHELF | | | | | | | | | | | |
| 001 | 22 | PQ | AA | | 2-7 | 22-11-32 | D00421C | 1 | | | TB0127H | 30 | 2 | | 050-099 |
| 001 | 22 | PQ | AA | | 2-8 | 22-11-32 | D00421C | 1 | | | TB0127H | 30 | 2 | | 150-199, 275-299 |
| 001Z | | | AA | | 0-0 | 22-11-32 | D00421C | DED | | | TB0127H | DED | | | ALL |
| 002 | 20 | PQ | AB | | 2-7 | 22-11-32 | D00421C | 2 | | | TB0127H | 30 | 2 | | 050-099 |
| 002 | 20 | PQ | AB | | 2-8 | 22-11-32 | D00421C | 2 | | | TB0127H | 30 | 2 | | 150-199, 275-299 |
| 002Z | | | AB | | 0-0 | 22-11-32 | D00421C | DED | | | TB0127H | DED | | | ALL |
| 003 | 22 | PQ | AC | | 5-1 | 22-11-32 | D04225P | 1 | | | TB0127H | 30 | 2 | | 050-099 |
| 003 | 22 | PQ | AC | | 5-3 | 22-11-32 | D04225P | 1 | | | TB0127H | 30 | 2 | | 150-199, 275-299 |
| 003Z | | | AC | | 0-0 | 22-11-32 | D04225P | DED | | | TB0127H | DED | | | ALL |
| 004 | 20 | PA | | | 1-11 | 22-11-31 | D00421C | 4 | | | GDX0007 | A.. | 2 | | ALL |
| 005 | 22 | PQ | AE | | 2-7 | 22-11-32 | D00421C | 5 | | | TB0127H | 30 | 2 | | 050-099 |
| 005 | 22 | PQ | AE | | 2-8 | 22-11-32 | D00421C | 5 | | | TB0127H | 30 | 2 | | 150-199, 275-299 |
| 005Z | | | AE | | 0-0 | 22-11-32 | D00421C | DED | | | TB0127H | DED | | | ALL |
| 006 | 22 | PA | | | 4-8 | 22-11-31 | D00421C | 6 | | | D04225P | 3 | | | ALL |
| 007 | 20 | PA | | | 1-11 | 22-11-31 | D00421C | 7 | | | GDX0007 | S.. | 2 | | ALL |
| 008 | 22 | PQ | AH | | 4-10 | 22-11-32 | D04241P | 7 | | | TB0127H | 41 | 2 | | 050-099 |
| 008 | 22 | PQ | AH | | 4-4 | 22-11-32 | D04241P | 7 | | | TB0127H | 41 | 2 | | 150-199, 275-299 |
| 008Z | | | AH | | 0-0 | 22-11-32 | D04241P | DED | | | TB0127H | DED | | | ALL |
| 009 | 20 | PQ | AI | | 2-11 | 22-11-32 | D00421C | 9 | | | TB0127H | 41 | 2 | | 050-099 |
| 009 | 20 | PQ | AI | | 2-5 | 22-11-32 | D00421C | 9 | | | TB0127H | 41 | 2 | | 150-199, 275-299 |
| 009Z | | | AI | | 0-0 | 22-11-32 | D00421C | DED | | | TB0127H | DED | | | ALL |
| 010 | 22 | PA | | | 4-3 | 22-11-32 | D04593P | 2 | | | TB0127G | 34 | 2 | | ALL |
| 011 | 22 | PQ | AK | | 4-3 | 22-11-32 | D04593P | 1 | | | TB0127H | 30 | 2 | | 050-099 |
| 011 | 22 | PQ | AK | | 4-0 | 22-11-32 | D04593P | 1 | | | TB0127H | 30 | 2 | | 150-199, 275-299 |
| 011Z | | | AK | | 0-0 | 22-11-32 | D04593P | DED | | | TB0127H | DED | | | ALL |
| 012 | 22 | PA | | | 2-7 | 22-11-32 | D00421B | H15 | | | TB0127G | 34 | 2 | | ALL |
| 013 | 22 | PA | | | 2-7 | 22-11-32 | D00421A | H15 | | | TB0127G | 34 | 2 | | ALL |
| 014 | 24 | PK | | | 2-7 | 22-15-12 | D00421A | F09 | | | TB0127G | 29 | 2 | | 050-099 |
| 014 | 24 | PK | | | 2-8 | 22-15-12 | D00421A | F09 | | | TB0127G | 29 | 2 | | 150-199, 275-299 |
| 015 | 22 | PA | | | 4-0 | 22-11-32 | D00421B | F15 | | | D04409P | 1 | | | ALL |
| 017 | 24 | PK | | | 4-4 | 22-11-32 | D04543P | 1 | | | TB0127G | 45 | 2 | | 050-099 |
| 017 | 24 | PK | | | 4-9 | 22-11-32 | D04543P | 1 | | | TB0127G | 45 | 2 | | 150-199, 275-299 |
| 018 | 22 | PA | | | 3-5 | 22-11-32 | D05625P | 22 | | | D00421B | H11 | | | ALL |
| 019 | 20 | PA | | | 3-7 | 22-11-32 | D04409P | 2 | | | GDX0006 | D.. | 2 | | ALL |
| 020 | 24 | PK | | | 0-7 | 22-11-32 | D00421B | A03 | | | D00421B | E04 | | | 050-099 |
| 020 | 24 | PK | | | 2-5 | 22-11-32 | D00421B | A03 | | | D00421B | E04 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11
Section W0120
Page 11
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0127 | 286T0127 | | | E1-4 C,SHELF (continued) | | | | | | | | | | | | | |
| 021 | 24 | | PK | 3-11 | 22-15-12 | D05625P | | 5 | | | | | TB0127G | 29 | 2 | | 050-099 |
| 021 | 24 | | PK | 4-0 | 22-15-12 | D05625P | | 5 | | | | | TB0127G | 29 | 2 | | 150-199, 275-299 |
| 022 | 24 | | PK | 0-7 | 22-11-32 | D00421A | | A13 | | | | | D00421A | A14 | | | 050-099 |
| 022 | 24 | | PK | 2-5 | 22-11-32 | D00421A | | A13 | | | | | D00421A | A14 | | | 150-199, 275-299 |
| 023 | 24 | | PK | 5-2 | 22-11-32 | D04543P | | 2 | | | | | TB0127G | 39 | 2 | | ALL |
| 024 | 24 | | PK | 2-11 | 22-11-32 | D00421B | | A06 | | | | | TB0127G | 45 | 2 | | 050-099 |
| 024 | 24 | | PK | 2-8 | 22-11-32 | D00421B | | A06 | | | | | TB0127G | 45 | 2 | | 150-199, 275-299 |
| 025 | 24 | | PK | 2-7 | 22-11-32 | D00421B | | C07 | | | | | TB0127G | 39 | 2 | | ALL |
| 026 | 22 | | PA | 4-4 | 22-11-32 | D00421A | | C15 | | | | | D04405P | 14 | | | ALL |
| 027 | 22 | | PA | 4-4 | 22-11-32 | D00421B | | C15 | | | | | D04405P | 11 | | | ALL |
| 028 | 22 | | PA | 4-2 | 22-11-32 | D00421B | | A15 | | | | | D04381P | 1 | | | ALL |
| 029 | 22 | | PA | 4-2 | 22-11-32 | D00421A | | A15 | | | | | D04381P | 32 | | | ALL |
| 030 | 24 | | PK | 0-7 | 22-11-32 | D00421A | | B13 | | | | | D00421A | B14 | | | 050-099 |
| 030 | 24 | | PK | 2-5 | 22-11-32 | D00421A | | B13 | | | | | D00421A | B14 | | | 150-199, 275-299 |
| 031 | 22 | | PA | 1-11 | 22-11-32 | D00421A | | A04 | | | | | GDX0007 | D.. | 2 | | ALL |
| 032 | 22 | | PA | 1-11 | 22-11-32 | D00421A | | G11 | | | | | GDX0007 | D.. | 2 | | ALL |
| 033 | 24 | | PK | 4-11 | 33-16-14 | D04705P | | 4 | | | | | TB0127F | C125 | 2 | | 050-099 |
| 033 | 24 | | PK | 5-1 | 33-16-14 | D04705P | | 4 | | | | | TB0127F | C125 | 2 | | 150-199, 275-299 |
| 034 | 22 | | PA | 4-2 | 22-11-32 | D00421B | | K15 | | | | | D04381P | 37 | | | ALL |
| 035 | 22 | | PA | 4-2 | 22-11-32 | D00421A | | K15 | | | | | D04381P | 40 | | | ALL |
| 036 | 22 | | PA | 2-3 | 22-11-22 | D05637J | | 1 | | | | | TB0127H | 41 | 2 | | 050-099 |
| 036 | 22 | | PA | 2-8 | 22-11-22 | D05637J | | 1 | | | | | TB0127H | 41 | 2 | | 150-199, 275-299 |
| 037 | 24 | | PK | 3-0 | 22-14-11 | D05625P | | 25 | | | | | D04305P | 11 | | | ALL |
| 039 | 22 | | PA | 4-0 | 22-12-31 | D00421A | | F15 | | | | | D04409P | 13 | | | ALL |
| 040 | 20 | | PA | 3-7 | 22-12-31 | D04409P | | 14 | | | | | GDX0006 | D.. | 2 | | ALL |
| 041 | 22 | | PA | 4-0 | 22-12-31 | D04409P | | 15 | | | | | D00421B | E09 | | | ALL |
| 042 | 24 | | PK | 2-11 | 22-15-12 | D05627J | | 13 | | | | | TB0127G | 29 | 2 | | 050-099 |
| 042 | 24 | | PK | 2-8 | 22-15-12 | D05627J | | 13 | | | | | TB0127G | 29 | 2 | | 150-199, 275-299 |
| 043 | 24 | | PK | 4-6 | 22-12-31 | D04881P | | 6 | | | | | D00421B | D08 | | | ALL |
| 044 | 24 | | PK | 4-6 | 22-12-31 | D00421B | | C09 | | | | | D04881P | 7 | | | ALL |
| 045 | 24 | | PK | 4-6 | 22-12-31 | D00421B | | D10 | | | | | D04881P | 8 | | | ALL |
| 046 | 24 | | PK | 4-6 | 22-12-31 | D00421B | | D09 | | | | | D04881P | 9 | | | ALL |
| 047 | 24 | | PK | 4-3 | 22-12-31 | D00421B | | E10 | | | | | D04421P | 6 | | | ALL |
| 048 | 24 | | PK | 3-5 | 22-13-31 | D00421B | | H03 | | | | | TB0127G | 75 | 2 | | 050-099 |
| 048 | 24 | | PK | 3-2 | 22-13-31 | D00421B | | H03 | | | | | TB0127G | 75 | 2 | | 150-199, 275-299 |
| 049 | 24 | | PK | 4-5 | 22-14-21 | D05557P | | 19 | | | | | TB0127H | 58 | 2 | | 050-099 |
| 049 | 24 | | PK | 4-7 | 22-14-21 | D05557P | | 19 | | | | | TB0127H | 58 | 2 | | 150-199, 275-299 |
| 050 | 22 | | PQ | BY | 4-5 | 22-14-21 | | 20 | | | | | TB0127H | 41 | 2 | | 050-099 |
| 050 | 22 | | PQ | BY | 4-11 | 22-14-21 | | 20 | | | | | TB0127H | 41 | 2 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 12

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0127 | 286T0127 | | | E1-4 C,SHELF (continued) | | | | | | | | | | | |
| 050Z | | | | BY | 0-0 | 22-14-21 | D05557P | | DED | | TB0127H | | DED | | ALL |
| 051 | 24 | PK | | | 4-5 | 22-14-21 | D05557P | | 18 | | TB0127H | 62 | 2 | | ALL |
| 052 | 24 | PK | | | 4-11 | 22-14-11 | D04175P | | 16 | | TB0127H | 62 | 2 | | ALL |
| 053 | 24 | PK | | | 4-11 | 22-14-11 | D04175P | | 17 | | TB0127H | 58 | 2 | | 050-099 |
| 053 | 24 | PK | | | 4-10 | 22-14-11 | D04175P | | 17 | | TB0127H | 58 | 2 | | 150-199, 275-299 |
| 054 | 22 | PQ | CD | | 4-11 | 22-14-11 | D04175P | | 13 | | TB0127H | 41 | 2 | | 050-099 |
| 054 | 22 | PQ | CD | | 4-5 | 22-14-11 | D04175P | | 13 | | TB0127H | 41 | 2 | | 150-199, 275-299 |
| 054Z | | | | CD | 0-0 | 22-14-11 | D04175P | | DED | | TB0127H | | DED | | ALL |
| 056 | 24 | PK | | | 3-7 | 22-14-21 | D05627J | | 8 | | TB0127G | 61 | 2 | | ALL |
| 057 | 24 | PK | | | 5-0 | 22-14-11 | D05455P | | 5 | | TB0127G | 61 | 2 | | ALL |
| 058 | 22 | PA | | | 2-6 | 22-11-12 | D05635P | | 1 | | TB0127H | 41 | 2 | | 050-099 |
| 058 | 22 | PA | | | 2-11 | 22-11-12 | D05635P | | 1 | | TB0127H | 41 | 2 | | 150-199, 275-299 |
| 059 | 24 | PK | | | 3-1 | 22-14-11 | D05625P | | 23 | | TB0127G | 61 | 2 | | ALL |
| 060 | 24 | PK | | | 2-8 | 22-14-31 | D05627J | | 2 | | D00421B | | K10 | | ALL |
| 061 | 24 | PK | | | 2-11 | 22-14-31 | D00421A | | G12 | | TB0127G | 61 | 2 | | ALL |
| 062 | 22 | PA | | | 2-5 | 22-14-31 | D00421A | | F03 | | TB0127F | | C137 | 2 | ALL |
| 063 | 24 | PK | | | 0-7 | 22-11-32 | D00421B | | K13 | | D00421B | | K14 | | 050-099 |
| 063 | 24 | PK | | | 2-5 | 22-11-32 | D00421B | | K13 | | D00421B | | K14 | | 150-199, 275-299 |
| 064 | 24 | PK | | | 2-11 | 22-14-31 | D00421B | | J12 | | TB0127H | 58 | 2 | | 050-099 |
| 064 | 24 | PK | | | 2-10 | 22-14-31 | D00421B | | J12 | | TB0127H | 58 | 2 | | 150-199, 275-299 |
| 065 | 24 | PK | | | 2-8 | 22-14-31 | D00421B | | J11 | | D05627J | 7 | | | ALL |
| 066 | 24 | PK | | | 3-5 | 22-14-31 | D00421A | | E12 | | D05625P | 24 | | | ALL |
| 067 | 24 | PK | | | 2-5 | 22-14-31 | D00421B | | E12 | | TB0127F | | C138 | 2 | ALL |
| 068 | 24 | PK | | | 2-11 | 22-14-31 | D00421B | | K02 | | TB0127G | 40 | 2 | | 050-099 |
| 068 | 24 | PK | | | 2-5 | 22-14-31 | D00421B | | K02 | | TB0127G | 40 | 2 | | 150-199, 275-299 |
| 069 | 22 | PA | | | 2-10 | 22-14-31 | D00421A | | F01 | | TB0127F | | A163 | 2 | ALL |
| 070 | 24 | PK | | | 2-7 | 22-14-31 | D00421B | | G12 | | TB0127G | 32 | 2 | | 050-099 |
| 070 | 24 | PK | | | 2-8 | 22-14-31 | D00421B | | G12 | | TB0127G | 32 | 2 | | 150-199, 275-299 |
| 071 | 24 | PK | | | 2-8 | 22-14-31 | D00421B | | K03 | | D05627J | 6 | | | ALL |
| 072 | 24 | PK | | | 2-8 | 22-14-31 | D00421B | | K11 | | D05627J | 1 | | | ALL |
| 073 | 24 | PK | | | 2-11 | 22-14-31 | D00421B | | K12 | | TB0127H | 62 | 2 | | ALL |
| 074 | 24 | PK | | | 0-7 | 22-11-32 | D00421B | | C13 | | D00421B | | F04 | | 050-099 |
| 074 | 24 | PK | | | 2-5 | 22-11-32 | D00421B | | C13 | | D00421B | | F04 | | 275-276 |
| 075 | 24 | PK | | | 5-5 | 22-14-31 | D05625P | | 4 | | D04815P | 9 | | | ALL |
| 076 | 24 | PK | | | 2-11 | 22-15-12 | D00421A | | G10 | | TB0127G | 43 | 2 | | 050-099 |
| 076 | 24 | PK | | | 2-5 | 22-15-12 | D00421A | | G10 | | TB0127G | 43 | 2 | | 150-199, 275-299 |
| 077 | 24 | PK | | | 3-1 | 22-15-12 | D05625P | | 10 | | TB0127G | 43 | 2 | | 050-099 |
| 077 | 24 | PK | | | 3-8 | 22-15-12 | D05625P | | 10 | | TB0127G | 43 | 2 | | 150-199, 275-299 |
| 078 | 24 | PK | | | 3-7 | 22-15-12 | D05627J | | 21 | | TB0127G | 43 | 2 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0120
Page 13
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0127 | 286T0127 | | | E1-4 C,SHELF (continued) | | | | | | | | | | | |
| 078 | 24 | | PK | | 3-0 | 22-15-12 | D05627J | | 21 | | TB0127G | 43 | 2 | | 150-199, 275-299 |
| 079 | 24 | | PK | | 2-5 | 22-15-12 | D00421A | | K03 | | TB0127F | A139 | 2 | | ALL |
| 080 | 24 | | PK | | 6-8 | 31-51-12 | D04241P | | 2 | | D04305P | 5 | | | ALL |
| 081 | 24 | | PK | | 2-10 | 22-15-12 | D00421A | | K01 | | TB0127F | A146 | 2 | | 050-099 |
| 081 | 24 | | PK | | 2-7 | 22-15-12 | D00421A | | K01 | | TB0127F | A146 | 2 | | 150-199, 275-299 |
| 082 | 24 | | PK | | 4-1 | 22-12-31 | D00421A | | F12 | | D04355P | 8 | | | ALL |
| 083 | 24 | | PK | | 4-1 | 22-12-31 | D00421B | | G09 | | D04355P | 9 | | | ALL |
| 084 | 24 | | PV | DI | 2-5 | 22-15-12 | D00421A | | G01 | | TB0127F | A138 | 2 | | ALL |
| 084Z | | | | DI | 0-0 | 22-15-12 | D00421A | | DED | | TB0127F | DED | | | ALL |
| 085 | 24 | | PK | | 4-1 | 22-12-31 | D00421A | | G09 | | D04355P | 7 | | | ALL |
| 086 | 24 | | PK | | 4-8 | 22-41-11 | D00421B | | C06 | | D04543P | 5 | | | ALL |
| 087 | 24 | | PK | | 2-5 | 22-41-11 | TB0127F | | A125 | 2 | D00421A | A03 | | | 050-099 |
| 087 | 24 | | PK | | 2-7 | 22-41-11 | TB0127F | | A125 | 2 | D00421A | A03 | | | 150-199, 275-299 |
| 089 | 24 | | PK | | 4-1 | 22-14-21 | D05627J | | 9 | | D05625P | 29 | | | ALL |
| 090 | 24 | | PV | DO | 2-5 | 22-15-12 | D00421A | | E03 | | TB0127F | A137 | 2 | | ALL |
| 090Z | | | | DO | 0-0 | 22-15-12 | D00421A | | DED | | TB0127F | DED | | | ALL |
| 092 | 24 | | PK | | 6-9 | 34-21-31 | D04815P | | 2 | | D04913P | 42 | | | ALL |
| 093 | 24 | | PK | | 6-9 | 34-21-31 | D04815P | | 3 | | D04913P | 43 | | | ALL |
| 094 | 24 | | PK | | 6-9 | 34-21-31 | D04815P | | 4 | | D04913P | 44 | | | ALL |
| 095 | 24 | | PK | | 2-5 | 22-41-13 | TB0127F | | A130 | 2 | D00421B | F10 | | | 050-099 |
| 095 | 24 | | PK | | 2-7 | 22-41-13 | TB0127F | | A130 | 2 | D00421B | F10 | | | 150-199, 275-299 |
| 096 | 24 | | PK | | 2-10 | 22-41-13 | TB0127F | | C146 | 2 | D00421B | F09 | | | 050-099 |
| 096 | 24 | | PK | | 2-7 | 22-41-13 | TB0127F | | C146 | 2 | D00421B | F09 | | | 150-199, 275-299 |
| 097 | 22 | | PQ | DV | 4-1 | 34-12-11 | D05635P | | 4 | | D04705P | 29 | | | ALL |
| 097Z | | | | DV | 0-0 | 34-12-11 | D05635P | | DED | | D04705P | DED | | | ALL |
| 098 | 22 | | PA | | 4-1 | 34-12-11 | D05635P | | 5 | | D04705P | 30 | | | ALL |
| 099 | 22 | | PA | | 3-8 | 27-61-11 | D04881P | | 5 | | D04355P | 2 | | | ALL |
| 101 | 20 | | PA | | 5-1 | 34-31-31 | D04241P | | 8 | | D00417C | 2 | | | ALL |
| 102 | 20 | | PA | | 1-10 | 34-31-31 | GDX0011 | | A.. | 2 | D00417C | 3 | | | ALL |
| 103 | 20 | | PA | | 1-10 | 34-31-31 | GDX0011 | | D.. | 2 | D00417C | 4 | | | ALL |
| 104 | 22 | | PA | | 0-7 | 34-31-31 | D00417B | | B03 | | D00417B | C03 | | | 050-099 |
| 104 | 22 | | PA | | 2-5 | 34-31-31 | D00417B | | B03 | | D00417B | C03 | | | 150-199, 275-299 |
| 105 | 22 | | PA | | 0-7 | 34-31-31 | D00417B | | B05 | | D00417B | C05 | | | 050-099 |
| 105 | 22 | | PA | | 2-5 | 34-31-31 | D00417B | | B05 | | D00417B | C05 | | | 150-199, 275-299 |
| 107 | 22 | | PA | | 5-3 | 34-31-31 | D04409P | | 5 | | TB0127G | 75 | 2 | | 050-099 |
| 107 | 22 | | PA | | 5-0 | 34-31-31 | D04409P | | 5 | | TB0127G | 75 | 2 | | 150-199, 275-299 |
| 108 | 22 | | PA | | 4-3 | 34-31-31 | D04409P | | 11 | | TB0127G | 23 | 2 | | 050-099 |
| 108 | 22 | | PA | | 3-11 | 34-31-31 | D04409P | | 11 | | TB0127G | 23 | 2 | | 150-199, 275-299 |
| 109 | 24 | | PK | | 3-10 | 34-33-31 | D04421P | | 5 | | TB0127G | 158 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 14

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0127 | 286T0127 | | | E1-4 C,SHELF (continued) | | | | | | | | | | | |
| 109 | 24 | | PK | | 4-1 | 34-33-31 | D04421P | | 5 | | TB0127G | 158 | 2 | | 150-199, 275-299 |
| 110 | 24 | | PK | | 2-9 | 34-31-31 | D00417B | | D15 | | TB0127G | 158 | 2 | | 050-099 |
| 110 | 24 | | PK | | 3-0 | 34-31-31 | D00417B | | D15 | | TB0127G | 158 | 2 | | 150-199, 275-299 |
| 111 | 24 | | PV | EK | 4-10 | 34-24-11 | D04241P | | 10 | | D01371C | 1 | | | ALL |
| 111Z | | | | EK | 0-0 | 34-24-11 | D04241P | | DED | | D01371C | DED | | | ALL |
| 112 | 24 | | PK | | 2-6 | 22-13-31 | D00417B | | C01 | | TB0127G | 75 | 2 | | 050-099 |
| 112 | 24 | | PK | | 2-9 | 22-13-31 | D00417B | | C01 | | TB0127G | 75 | 2 | | 150-199, 275-299 |
| 113 | 22 | | PQ | EM | 4-1 | 34-12-11 | D05635P | | 6 | | D04705P | 31 | | | ALL |
| 113Z | | | | EM | 0-0 | 34-12-11 | D05635P | | DED | | D04705P | DED | | | ALL |
| 114 | 20 | | PA | | 1-10 | 34-24-11 | D01371C | | 4 | | GDX0010 | D.. | 2 | | ALL |
| 115 | 20 | | PQ | EO | 4-10 | 34-24-11 | D04241P | | 11 | | D01371C | 5 | | | ALL |
| 115Z | | | | EO | 0-0 | 34-24-11 | D04241P | | DED | | D01371C | DED | | | ALL |
| 116 | 20 | | PA | | 1-10 | 34-24-11 | D01371C | | 6 | | GDX0010 | D.. | 2 | | ALL |
| 117 | 24 | | PK | | 2-11 | 22-13-31 | D00421B | | H02 | | TB0127G | 44 | 2 | | 050-099 |
| 117 | 24 | | PK | | 2-5 | 22-13-31 | D00421B | | H02 | | TB0127G | 44 | 2 | | 150-199, 275-299 |
| 118 | 22 | | PA | | 5-0 | 34-22-36 | D05455P | | 23 | | TB0127G | 44 | 2 | | 050-099 |
| 118 | 22 | | PA | | 4-5 | 34-22-36 | D05455P | | 23 | | TB0127G | 44 | 2 | | 150-199, 275-299 |
| 139 | 24 | | PK | | 0-7 | 22-11-32 | D00421B | | D03 | | D00421B | K04 | | | 050-099 |
| 139 | 24 | | PK | | 2-5 | 22-11-32 | D00421B | | D03 | | D00421B | K04 | | | 150-199, 275-299 |
| 144 | 24 | | PK | | 0-7 | 22-11-32 | D00421B | | K09 | | D00421B | F11 | | | 050-099, 150-199, 277-299 |
| 152 | 24 | | PK | | 4-11 | 34-24-11 | D05455P | | 10 | | D01371A | D02 | | | ALL |
| 153 | 24 | | PK | | 4-11 | 34-24-11 | D05455P | | 13 | | D01371A | A02 | | | ALL |
| 154 | 24 | | PK | | 5-5 | 34-24-11 | D05455P | | 16 | | TB0127G | 82 | 2 | | ALL |
| 156 | 24 | | PK | | 2-7 | 34-24-11 | D01371A | | C02 | | TB0127G | 82 | 2 | | 050-099, 153-199, 275-299 |
| 156 | 24 | | PK | | 2-7 | 34-24-11 | TB0127G | | 82 | 2 | D01371A | B02 | | | 150-152 |
| 160 | 24 | | PK | | 5-5 | 34-24-11 | D05455P | | 19 | | TB0127G | 82 | 2 | | 050-099, 150-199 |
| 160 | 24 | | PK | | 5-5 | 34-24-11 | D05455P | | 19 | | D01371A | B02 | | | 275-299 |
| 161 | 24 | | PK | | 2-9 | 34-46-12 | D05627J | | 15 | | TB0127F | A014 | 2 | | 050-099, 150-199, 275-278 |
| 162 | 24 | | PK | | 6-0 | 34-22-37 | D04913P | | 9 | | TB0127F | C106 | 2 | | 050-099 |
| 162 | 24 | | PK | | 6-3 | 34-22-37 | D04913P | | 9 | | TB0127F | C106 | 2 | | 150-199, 275-299 |
| 185 | 22 | | PA | | 3-8 | 22-24-11 | D04355P | | 1 | | D04881P | 1 | | | ALL |
| 192 | 22 | | PA | | 3-6 | 22-21-11 | D04913P | | 35 | | D04355P | 22 | | | ALL |
| 194 | 20 | | PA | | 1-10 | 34-24-11 | D01371C | | 2 | | GDX0010 | S.. | 2 | | ALL |
| 204B | 20 | | PB | ID | 2-7 | 22-11-31 | D00421C | | 11 | | TB0127H | 35 | 2 | | ALL |
| 204R | 20 | | PB | ID | 0-0 | 22-11-31 | D00421C | | 10 | | TB0127H | 37 | 2 | | ALL |
| 205B | 22 | | PB | IE | 4-9 | 22-11-31 | D04405P | | 2 | | TB0127H | 35 | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0120
Page 15
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0127 | 286T0127 | | | E1-4 C,SHELF (continued) | | | | | | | | | | | | |
| 205R | 22 | PB | IE | 0-0 | 22-11-31 | D04405P | | 1 | | | | TB0127H | 37 | 2 | | ALL |
| 206B | 22 | PB | IF | 4-8 | 22-11-31 | D04381P | | 6 | | | | TB0127H | 35 | 2 | | ALL |
| 206R | 22 | PB | IF | 0-0 | 22-11-31 | D04381P | | 5 | | | | TB0127H | 37 | 2 | | ALL |
| 207B | 22 | PB | IG | 4-8 | 22-11-31 | D04381P | | 8 | | | | TB0127H | 35 | 2 | | ALL |
| 207R | 22 | PB | IG | 0-0 | 22-11-31 | D04381P | | 7 | | | | TB0127H | 37 | 2 | | ALL |
| 208B | 24 | PW | IH | 2-11 | 22-12-31 | D00421B | | B04 | | | | TB0127H | 52 | 2 | | 050-099 |
| 208B | 24 | PW | IH | 2-8 | 22-12-31 | D00421B | | B04 | | | | TB0127H | 52 | 2 | | 150-199, 275-299 |
| 208R | 24 | PW | IH | 0-0 | 22-12-31 | D00421B | | B03 | | | | TB0127H | 50 | 2 | | ALL |
| 208Z | | | IH | 0-0 | 22-12-31 | D00421B | | DED | | | | GDY0008 | S.. | 2 | | ALL |
| 211B | 22 | PB | IK | 4-2 | 22-12-31 | D00421B | | D11 | | | | D04381P | 10 | | | ALL |
| 211R | 22 | PB | IK | 0-0 | 22-12-31 | D00421B | | E11 | | | | D04381P | 9 | | | ALL |
| 212 | 20 | UA | | 1-6 | 22-12-31 | D00421B | | | | | FC | GDY0007 | S.. | 2 | | ALL |
| 212B | 24 | PW | IL | 4-3 | 22-12-31 | D00421B | | C02 | | | | D04421P | 8 | | | ALL |
| 212R | 24 | PW | IL | 0-0 | 22-12-31 | D00421B | | C01 | | | | D04421P | 7 | | | ALL |
| 212Z | | | IL | 0-0 | 22-12-31 | D00421B | | | | | FC | D04421P | 9 | | | ALL |
| 213B | 24 | PW | IM | 2-10 | 22-12-31 | D00421A | | D09 | | | | TB0127G | 141 | 2 | | 050-099 |
| 213B | 24 | PW | IM | 2-5 | 22-12-31 | D00421A | | D09 | | | | TB0127G | 141 | 2 | | 150-199, 275-299 |
| 213R | 24 | PW | IM | 0-0 | 22-12-31 | D00421A | | C09 | | | | TB0127G | 140 | 2 | | ALL |
| 213Z | | | IM | 0-0 | 22-12-31 | D00421A | | DED | | | | GDY0007 | S.. | 2 | | ALL |
| 214B | 24 | PW | IN | 4-11 | 22-12-31 | D04593P | | 4 | | | | TB0127H | 52 | 2 | | 050-099 |
| 214B | 24 | PW | IN | 4-7 | 22-12-31 | D04593P | | 4 | | | | TB0127H | 52 | 2 | | 150-199, 275-299 |
| 214R | 24 | PW | IN | 0-0 | 22-12-31 | D04593P | | 3 | | | | TB0127H | 50 | 2 | | ALL |
| 214Z | | | IN | 0-0 | 22-12-31 | D04593P | | 5 | | | | GDY0008 | S.. | 2 | | ALL |
| 216B | 24 | PW | IP | 2-11 | 22-12-31 | D00421B | | B02 | | | | TB0127G | 57 | 2 | | 050-099 |
| 216B | 24 | PW | IP | 2-10 | 22-12-31 | D00421B | | B02 | | | | TB0127G | 57 | 2 | | 150-199, 275-299 |
| 216R | 24 | PW | IP | 0-0 | 22-12-31 | D00421B | | B01 | | | | TB0127G | 56 | 2 | | ALL |
| 216Z | | | IP | 0-0 | 22-12-31 | D00421B | | DED | | | | GDY0009 | S.. | 2 | | ALL |
| 217B | 24 | PW | IQ | 3-7 | 22-12-31 | D05627J | | 4 | | | | TB0127G | 57 | 2 | | 050-099 |
| 217B | 24 | PW | IQ | 3-5 | 22-12-31 | D05627J | | 4 | | | | TB0127G | 57 | 2 | | 150-199, 275-299 |
| 217R | 24 | PW | IQ | 0-0 | 22-12-31 | D05627J | | 3 | | | | TB0127G | 56 | 2 | | ALL |
| 217Z | | | IQ | 0-0 | 22-12-31 | D05627J | | 5 | | | | GDY0009 | S.. | 2 | | ALL |
| 218B | 24 | PW | IR | 3-11 | 22-12-31 | D04913P | | 11 | | | | TB0127G | 57 | 2 | | 050-099 |
| 218B | 24 | PW | IR | 4-2 | 22-12-31 | D04913P | | 11 | | | | TB0127G | 57 | 2 | | 150-199, 275-299 |
| 218R | 24 | PW | IR | 0-0 | 22-12-31 | D04913P | | 10 | | | | TB0127G | 56 | 2 | | ALL |
| 218Z | | | IR | 0-0 | 22-12-31 | D04913P | | 12 | | | | GDY0009 | S.. | 2 | | ALL |
| 219B | 24 | PW | IS | 2-5 | 22-12-31 | D00421A | | B10 | | | | TB0127F | C134 | 2 | | ALL |
| 219R | 24 | PW | IS | 0-0 | 22-12-31 | D00421A | | A10 | | | | TB0127F | A134 | 2 | | ALL |
| 219Z | | | IS | 0-0 | 22-12-31 | D00421A | | DED | | | | GDY0006 | S.. | 2 | | ALL |
| 223B | 24 | PW | IW | 2-5 | 22-13-31 | D00421A | | B09 | | | | TB0127F | C135 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 16

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0127 | 286T0127 | | | E1-4 C,SHELF (continued) | | | | | | | | | | | |
| 223R | 24 | PW | IW | | 0-0 | 22-13-31 | D00421A | A09 | | | TB0127F | A135 | 2 | | ALL |
| 223Z | | | IW | | 0-0 | 22-13-31 | D00421A | DED | | | GDY0006 | S.. | 2 | | ALL |
| 224 | 20 | UA | | | 1-6 | 22-13-31 | D00417B | | | FK | GDX0011 | S.. | 2 | | ALL |
| 224B | 24 | PW | IX | | 3-2 | 22-13-31 | D00417B | C07 | | | D00421B | A02 | | | ALL |
| 224R | 24 | PW | IX | | 0-0 | 22-13-31 | D00417B | B07 | | | D00421B | A01 | | | ALL |
| 224Z | | | IX | | 0-0 | 22-13-31 | D00417B | | | FK | D00421B | DED | | | ALL |
| 225B | 24 | PW | IY | | 3-5 | 22-13-31 | TB0127G | 19 | 2 | | D00421B | E02 | | | ALL |
| 225R | 24 | PW | IY | | 0-0 | 22-13-31 | TB0127G | 18 | 2 | | D00421B | E01 | | | ALL |
| 225Z | | | IY | | 0-0 | 22-13-31 | GDY0002 | S.. | 2 | | D00421B | DED | | | ALL |
| 226B | 22 | PB | JA | | 4-4 | 22-13-31 | D04405P | 4 | | | D00421B | E06 | | | ALL |
| 226R | 22 | PB | JA | | 0-0 | 22-13-31 | D04405P | 3 | | | D00421B | F06 | | | ALL |
| 227B | 22 | PB | JB | | 4-2 | 22-13-31 | D04381P | 18 | | | D00421B | E07 | | | ALL |
| 227R | 22 | PB | JB | | 0-0 | 22-13-31 | D04381P | 17 | | | D00421B | F07 | | | ALL |
| 230B | 24 | PW | JE | | 2-5 | 22-15-11 | D00421A | H03 | | | TB0127F | C133 | 2 | | ALL |
| 230R | 24 | PW | JE | | 0-0 | 22-15-11 | D00421A | G03 | | | TB0127F | A133 | 2 | | ALL |
| 230Z | | | JE | | 0-0 | 22-15-11 | D00421A | DED | | | GDY0006 | S.. | 2 | | ALL |
| 231 | 20 | UA | | | 1-6 | 22-15-11 | D00421B | | | FM | GDX0007 | S.. | 2 | | ALL |
| 231B | 24 | PW | JF | | 3-5 | 22-15-11 | D00421B | F03 | | | D05625P | 8 | | | ALL |
| 231R | 24 | PW | JF | | 0-0 | 22-15-11 | D00421B | E03 | | | D05625P | 7 | | | ALL |
| 231Z | | | JF | | 0-0 | 22-15-11 | D00421B | | | FM | D05625P | 9 | | | ALL |
| 232B | 24 | PW | JG | | 2-10 | 22-15-11 | D00421A | E01 | | | TB0127F | C159 | 2 | | 050-099 |
| 232B | 24 | PW | JG | | 2-9 | 22-15-11 | D00421A | E01 | | | TB0127F | C159 | 2 | | 150-199, 275-299 |
| 232R | 24 | PW | JG | | 0-0 | 22-15-11 | D00421A | D01 | | | TB0127F | A159 | 2 | | ALL |
| 232Z | | | JG | | 0-0 | 22-15-11 | D00421A | DED | | | GDY0009 | S.. | 2 | | ALL |
| 233 | 20 | UA | | | 1-6 | 22-15-11 | D00421B | | | FO | GDX0006 | S.. | 2 | | ALL |
| 233B | 24 | PW | JH | | 2-8 | 22-15-11 | D00421B | F02 | | | D05627J | 11 | | | ALL |
| 233R | 24 | PW | JH | | 0-0 | 22-15-11 | D00421B | F01 | | | D05627J | 10 | | | ALL |
| 233Z | | | JH | | 0-0 | 22-15-11 | D00421B | | | FO | D05627J | 12 | | | ALL |
| 236B | 24 | PW | JK | | 3-9 | 22-22-11 | D04355P | 4 | | | TB0127H | 52 | 2 | | 050-099 |
| 236B | 24 | PW | JK | | 4-2 | 22-22-11 | D04355P | 4 | | | TB0127H | 52 | 2 | | 150-199, 275-299 |
| 236R | 24 | PW | JK | | 0-0 | 22-22-11 | D04355P | 3 | | | TB0127H | 50 | 2 | | ALL |
| 236Z | | | JK | | 0-0 | 22-22-11 | D04355P | 5 | | | GDY0008 | S.. | 2 | | ALL |
| 238 | 20 | UA | | | 1-6 | 22-41-11 | D00421B | | | FR | GDX0006 | S.. | 2 | | ALL |
| 238B | 24 | PW | JM | | 4-3 | 22-41-11 | D00421B | C04 | | | D04913P | 14 | | | ALL |
| 238R | 24 | PW | JM | | 0-0 | 22-41-11 | D00421B | C03 | | | D04913P | 13 | | | ALL |
| 238Z | | | JM | | 0-0 | 22-41-11 | D00421B | | | FR | D04913P | 15 | | | ALL |
| 239B | 24 | PW | JN | | 2-10 | 22-41-12 | TB0127F | C156 | 2 | | D00421A | A02 | | | 050-099 |
| 239B | 24 | PW | JN | | 2-9 | 22-41-12 | TB0127F | C156 | 2 | | D00421A | A02 | | | 150-199, 275-299 |
| 239R | 24 | PW | JN | | 0-0 | 22-41-12 | TB0127F | A156 | 2 | | D00421A | A01 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0120
Page 17
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0127 | 286T0127 | | | E1-4 C,SHELF (continued) | | | | | | | | | | | | |
| 239Z | | | | JN | 0-0 | 22-41-12 | D00421A | DED | | | | | GDY0009 | S.. | 2 | 050-099, 152-199, 275-299 |
| 239Z | | | | JN | 0-0 | 22-41-12 | D00421A | DED | | | | | GDY0010 | S.. | 2 | 150-151 |
| 248B | 24 | PL | | JW | 4-1 | 22-12-31 | D04355P | 24 | | | | | D00421B | F13 | | ALL |
| 248R | 24 | PL | | JW | 0-0 | 22-12-31 | D04355P | 23 | | | | | D00421B | E13 | | ALL |
| 249B | 24 | PW | | JX | 4-3 | 31-31-20 | D04333P | 22 | | | | | TB0127Z | 154 | % | 050-099 |
| 249B | 24 | PW | | JX | 4-6 | 31-31-20 | D04333P | 22 | | | | | TB0127Z | 154 | % | 150-199, 275-299 |
| 249R | 24 | PW | | JX | 0-0 | 31-31-20 | D04333P | 21 | | | | | TB0127Z | 153 | % | ALL |
| 249Z | | | | JX | 0-0 | 31-31-20 | D04333P | 20 | | | | | TB0127Z | DED | | ALL |
| 250 | 20 | UA | | | 1-6 | 31-35-13 | D00421B | REF | | JY | | | GDY0007 | S.. | 2 | ALL |
| 250B | 24 | PW | | JY | 4-3 | 31-35-13 | D00421B | D02 | | | | | D04913P | 29 | | ALL |
| 250R | 24 | PW | | JY | 0-0 | 31-35-13 | D00421B | D01 | | | | | D04913P | 28 | | ALL |
| 250Z | | | | JY | 0-0 | 31-35-13 | D00421B | REF | | JY | | | D04913P | 30 | | ALL |
| 251B | 24 | PL | | KA | 2-6 | 23-51-13 | D00417B | B01 | | | | | TB0127F | C074 | 2 | 050-099 |
| 251B | 24 | PL | | KA | 2-9 | 23-51-13 | D00417B | B01 | | | | | TB0127F | C074 | 2 | 150-199, 275-299 |
| 251R | 24 | PL | | KA | 0-0 | 23-51-13 | D00417B | A01 | | | | | TB0127F | A074 | 2 | ALL |
| 252B | 24 | PW | | KB | 3-8 | 34-31-31 | D00417B | C11 | | | | | TB0127G | 22 | 2 | 050-099 |
| 252B | 24 | PW | | KB | 4-0 | 34-31-31 | D00417B | C11 | | | | | TB0127G | 22 | 2 | 150-199, 275-299 |
| 252R | 24 | PW | | KB | 0-0 | 34-31-31 | D00417B | B11 | | | | | TB0127G | 21 | 2 | ALL |
| 252Z | | | | KB | 0-0 | 34-31-31 | D00417B | DED | | | | | GDY0005 | S.. | 2 | ALL |
| 253B | 24 | PW | | KC | 3-4 | 34-24-11 | D01371A | B01 | | | | | TB0127G | 22 | 2 | 050-099 |
| 253B | 24 | PW | | KC | 3-8 | 34-24-11 | D01371A | B01 | | | | | TB0127G | 22 | 2 | 150-199, 275-299 |
| 253R | 24 | PW | | KC | 0-0 | 34-24-11 | D01371A | A01 | | | | | TB0127G | 21 | 2 | ALL |
| 253Z | | | | KC | 0-0 | 34-24-11 | D01371A | DED | | | | | GDY0005 | S.. | 2 | ALL |
| 254B | 22 | PB | | KD | 5-1 | 34-31-31 | D00417B | C15 | | | | | D04409P | 8 | | ALL |
| 254R | 22 | PB | | KD | 0-0 | 34-31-31 | D00417B | B15 | | | | | D04409P | 9 | | ALL |
| 255 | 20 | UA | | | 1-6 | 34-31-31 | D00417B | | | FV | | | GDY0011 | S.. | 2 | ALL |
| 255B | 24 | PW | | KE | 5-1 | 34-31-31 | D00417B | C13 | | | | | D04409P | 7 | | ALL |
| 255R | 24 | PW | | KE | 0-0 | 34-31-31 | D00417B | B13 | | | | | D04409P | 6 | | ALL |
| 255Z | | | | KE | 0-0 | 34-31-31 | D00417B | | | FV | | | D04409P | 12 | | ALL |
| 256B | 24 | PL | | KF | 4-11 | 34-24-11 | D05455P | 2 | | | | | D01371A | B05 | | ALL |
| 256R | 24 | PL | | KF | 0-0 | 34-24-11 | D05455P | 1 | | | | | D01371A | A05 | | ALL |
| 257B | 24 | PL | | KG | 4-11 | 34-24-11 | D05455P | 9 | | | | | D01371A | F01 | | ALL |
| 257R | 24 | PL | | KG | 0-0 | 34-24-11 | D05455P | 8 | | | | | D01371A | E01 | | ALL |
| 258B | 24 | PL | | KH | 4-11 | 34-24-11 | D05455P | 12 | | | | | D01371A | J01 | | ALL |
| 258R | 24 | PL | | KH | 0-0 | 34-24-11 | D05455P | 11 | | | | | D01371A | H01 | | ALL |
| 259B | 24 | PL | | KI | 4-11 | 34-24-11 | D05455P | 15 | | | | | D01371A | B03 | | ALL |
| 259R | 24 | PL | | KI | 0-0 | 34-24-11 | D05455P | 14 | | | | | D01371A | A03 | | ALL |
| 260B | 24 | PL | | KJ | 4-11 | 34-24-11 | D05455P | 18 | | | | | D01371A | E03 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 18

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0127 | 286T0127 | | | E1-4 C,SHELF (continued) | | | | | | | | | | | |
| 260R | 24 | PL | KJ | 0-0 | 34-24-11 | D05455P | 17 | | | | D01371A | D03 | | | ALL |
| 266 | 20 | UA | | 2-1 | 32-45-11 | D13366B | REF | KP | | | GDX0002 | S.. | 2 | | 050-099, 150-199 |
| 266B | 24 | PW | KP | 6-2 | 32-45-11 | D13366B | B05 | | | | D04305P | 17 | | | 050-099, 150-199 |
| 266R | 24 | PW | KP | 0-0 | 32-45-11 | D13366B | A05 | | | | D04305P | 16 | | | 050-099, 150-199 |
| 266Z | | | KP | 0-0 | 32-45-11 | D13366B | REF | KP | | | D04305P | 18 | | | 050-099, 150-199 |
| 267B | 24 | PW | KQ | 6-5 | 32-45-12 | D13366B | B04 | | | | D04705P | 22 | | | 050-099, 150-199 |
| 267R | 24 | PW | KQ | 0-0 | 32-45-12 | D13366B | A04 | | | | D04705P | 21 | | | 050-099, 150-199 |
| 267Z | | | KQ | 0-0 | 32-45-12 | D13366B | C04 | | | | D04705P | 17 | | | 050-099, 150-199 |
| 268B | 24 | PW | KR | 6-5 | 32-45-12 | D13366B | B03 | | | | D04705P | 28 | | | 050-099, 150-199 |
| 268R | 24 | PW | KR | 0-0 | 32-45-12 | D13366B | A03 | | | | D04705P | 27 | | | 050-099, 150-199 |
| 268Z | | | KR | 0-0 | 32-45-12 | D13366B | C03 | | | | D04705P | 23 | | | 050-099, 150-199 |
| 269B | 24 | PW | KS | 6-1 | 32-45-13 | D13366A | B02 | | | | D04355P | 13 | | | 050-099, 150-199 |
| 269R | 24 | PW | KS | 0-0 | 32-45-13 | D13366A | A02 | | | | D04355P | 14 | | | 050-099, 150-199 |
| 269Z | | | KS | 0-0 | 32-45-13 | D13366A | C02 | | | | D04355P | 15 | | | 050-099, 150-199 |
| 270B | 24 | PW | KT | 6-1 | 32-45-13 | D13366A | B03 | | | | D04355P | 16 | | | 050-099, 150-199 |
| 270R | 24 | PW | KT | 0-0 | 32-45-13 | D13366A | A03 | | | | D04355P | 17 | | | 050-099, 150-199 |
| 270Z | | | KT | 0-0 | 32-45-13 | D13366A | C03 | | | | D04355P | 18 | | | 050-099, 150-199 |
| 281B | 24 | PW | LF | 3-4 | 34-22-82 | D04175P | 2 | | | | TB0127G | 19 | 2 | | ALL |
| 281R | 24 | PW | LF | 0-0 | 34-22-82 | D04175P | 1 | | | | TB0127G | 18 | 2 | | ALL |
| 281Z | | | LF | 0-0 | 34-22-82 | D04175P | 3 | | | | GDY0002 | S.. | 2 | | ALL |
| 282B | 24 | PW | LG | 6-1 | 34-22-38 | D04913P | 5 | | | | TB0127G | 19 | 2 | | ALL |
| 282R | 24 | PW | LG | 0-0 | 34-22-38 | D04913P | 4 | | | | TB0127G | 18 | 2 | | ALL |
| 282Z | | | LG | 0-0 | 34-22-38 | D04913P | 6 | | | | GDY0002 | S.. | 2 | | ALL |
| 283B | 24 | PW | LH | 6-1 | 34-22-39 | D04421P | 3 | | | | TB0127G | 16 | 2 | | ALL |
| 283R | 24 | PW | LH | 0-0 | 34-22-39 | D04421P | 2 | | | | TB0127G | 15 | 2 | | ALL |
| 283Z | | | LH | 0-0 | 34-22-39 | D04421P | 1 | | | | GDY0002 | S.. | 2 | | ALL |
| 290B | 24 | PW | LO | 6-9 | 34-22-81 | D04175P | 7 | | | | D04913P | 40 | | | ALL |
| 290R | 24 | PW | LO | 0-0 | 34-22-81 | D04175P | 6 | | | | D04913P | 39 | | | ALL |
| 290Z | | | LO | 0-0 | 34-22-81 | D04175P | 8 | | | | D04913P | 41 | | | ALL |
| 291B | 24 | PL | LP | 3-2 | 27-32-11 | D04881P | 3 | | | | D05625P | 31 | | | ALL |
| 291R | 24 | PL | LP | 0-0 | 27-32-11 | D04881P | 2 | | | | D05625P | 30 | | | ALL |
| 297B | 24 | PW | LV | 6-1 | 32-45-13 | D13366A | B06 | | | | D04355P | 28 | | | 050-099, 150-199 |
| 297R | 24 | PW | LV | 0-0 | 32-45-13 | D13366A | A06 | | | | D04355P | 29 | | | 050-099, 150-199 |
| 297Z | | | LV | 0-0 | 32-45-13 | D13366A | C06 | | | | D04355P | 30 | | | 050-099, 150-199 |
| 298B | 24 | PW | LW | 6-1 | 32-45-13 | D13366A | B07 | | | | D04355P | 31 | | | 050-099, 150-199 |
| 298R | 24 | PW | LW | 0-0 | 32-45-13 | D13366A | A07 | | | | D04355P | 32 | | | 050-099, 150-199 |
| 298Z | | | LW | 0-0 | 32-45-13 | D13366A | C07 | | | | D04355P | 33 | | | 050-099, 150-199 |
| 302B | 22 | PC | MB | 4-2 | 22-12-31 | D00421A | H10 | | | | D04381P | 15 | | | ALL |
| 302R | 22 | PC | MB | 0-0 | 22-12-31 | D00421A | J09 | | | | D04381P | 14 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0120
Page 19
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0127 | 286T0127 | | | E1-4 C,SHELF (continued) | | | | | | | | | | | | |
| 302Y | 22 | PC | MB | 0-0 | 22-12-31 | D00421A | H09 | | | | D04381P | 16 | | | ALL | |
| 303B | 22 | PC | MC | 4-2 | 22-12-31 | D00421B | H10 | | | | D04381P | 12 | | | ALL | |
| 303R | 22 | PC | MC | 0-0 | 22-12-31 | D00421B | J09 | | | | D04381P | 11 | | | ALL | |
| 303Y | 22 | PC | MC | 0-0 | 22-12-31 | D00421B | H09 | | | | D04381P | 13 | | | ALL | |
| 305B | 22 | PC | ME | 4-4 | 22-13-31 | D04405P | 6 | | | | D00421B | K06 | | | ALL | |
| 305R | 22 | PC | ME | 0-0 | 22-13-31 | D04405P | 5 | | | | D00421B | J05 | | | ALL | |
| 305Y | 22 | PC | ME | 0-0 | 22-13-31 | D04405P | 7 | | | | D00421B | K05 | | | ALL | |
| 306B | 22 | PC | MF | 4-4 | 22-13-31 | D04405P | 9 | | | | D00421A | K06 | | | ALL | |
| 306R | 22 | PC | MF | 0-0 | 22-13-31 | D04405P | 8 | | | | D00421A | J05 | | | ALL | |
| 306Y | 22 | PC | MF | 0-0 | 22-13-31 | D04405P | 10 | | | | D00421A | K05 | | | ALL | |
| 307B | 22 | PC | MG | 4-2 | 22-13-31 | D04381P | 20 | | | | D00421B | J06 | | | ALL | |
| 307R | 22 | PC | MG | 0-0 | 22-13-31 | D04381P | 19 | | | | D00421B | H06 | | | ALL | |
| 307Y | 22 | PC | MG | 0-0 | 22-13-31 | D04381P | 21 | | | | D00421B | H05 | | | ALL | |
| 308B | 22 | PC | MH | 4-2 | 22-13-31 | D04381P | 23 | | | | D00421A | J06 | | | ALL | |
| 308R | 22 | PC | MH | 0-0 | 22-13-31 | D04381P | 22 | | | | D00421A | H06 | | | ALL | |
| 308Y | 22 | PC | MH | 0-0 | 22-13-31 | D04381P | 24 | | | | D00421A | H05 | | | ALL | |
| 390B | 24 | PM | PO | 4-11 | 34-24-11 | D05455P | 21 | | | | D01371C | 10 | | | ALL | |
| 390R | 24 | PM | PO | 0-0 | 34-24-11 | D05455P | 20 | | | | D01371C | 9 | | | ALL | |
| 390Y | 24 | PM | PO | 0-0 | 34-24-11 | D05455P | 22 | | | | D01371C | 11 | | | ALL | |
| 516B | 24 | PW | UP | 3-5 | 34-12-61 | D05625P | 2 | | | | D04333P | 13 | | | ALL | |
| 516R | 24 | PW | UP | 0-0 | 34-12-61 | D05625P | 1 | | | | D04333P | 14 | | | ALL | |
| 516Z | | | UP | 0-0 | 34-12-61 | D05625P | 3 | | | | D04333P | 15 | | | ALL | |
| 523B | 22 | PR | UW | 4-3 | 34-12-11 | D05635P | 3 | | | | D05557P | 22 | | | ALL | |
| 523R | 22 | PR | UW | 0-0 | 34-12-11 | D05635P | 2 | | | | D05557P | 21 | | | ALL | |
| 523Z | | | UW | 0-0 | 34-12-11 | D05635P | DED | | | | D05557P | DED | | | ALL | |
| 524B | 22 | PR | UX | 4-8 | 34-12-11 | D05635P | 8 | | | | D05553P | 7 | | | ALL | |
| 524R | 22 | PR | UX | 0-0 | 34-12-11 | D05635P | 7 | | | | D05553P | 6 | | | ALL | |
| 524Z | | | UX | 0-0 | 34-12-11 | D05635P | DED | | | | D05553P | DED | | | ALL | |
| 535B | 24 | PW | VJ | 3-6 | 22-21-11 | D04913P | 34 | | | | D04355P | 21 | | | ALL | |
| 535R | 24 | PW | VJ | 0-0 | 22-21-11 | D04913P | 33 | | | | D04355P | 20 | | | ALL | |
| 535Z | | | VJ | 0-0 | 22-21-11 | D04913P | 32 | | | | D04355P | 19 | | | ALL | |
| 537B | 24 | PW | VL | 2-11 | 32-42-11 | D04705P | 25 | | | | D04913P | 37 | | | 050-099 | |
| 537B | 24 | PW | VL | 5-0 | 32-42-11 | D04705P | 25 | | | | D04913P | 37 | | | 150-199, 275-299 | |
| 537R | 24 | PW | VL | 0-0 | 32-42-11 | D04705P | 24 | | | | D04913P | 36 | | | ALL | |
| 537Z | | | VL | 0-0 | 32-42-11 | D04705P | 26 | | | | D04913P | 38 | | | ALL | |
| 539B | 24 | PW | VN | 5-2 | 31-31-20 | D04333P | 4 | | | | TB0127G | 22 | 2 | | 050-099 | |
| 539B | 24 | PW | VN | 6-0 | 31-31-20 | D04333P | 4 | | | | TB0127G | 22 | 2 | | 150-199, 275-299 | |
| 539R | 24 | PW | VN | 0-0 | 31-31-20 | D04333P | 3 | | | | TB0127G | 21 | 2 | | ALL | |
| 539Z | | | VN | 0-0 | 31-31-20 | D04333P | 5 | | | | GDY0005 | S.. | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 20

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|---------------------------------|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0127 | 286T0127 | E1-4 C,SHELF (continued) | | | | | | | | | | | | | |
| 540B | 24 | PW | VO | | 6-7 | 31-31-20 | D04333P | | 18 | | TB0127G | 16 | 2 | | ALL |
| 540R | 24 | PW | VO | | 0-0 | 31-31-20 | D04333P | | 17 | | TB0127G | 15 | 2 | | ALL |
| 540Z | | | VO | | 0-0 | 31-31-20 | D04333P | | 19 | | GDY0002 | S.. | 2 | | ALL |
| 543B | 24 | PW | VR | | 3-10 | 34-16-11 | D05635P | | 14 | | D04305P | 9 | | | ALL |
| 543R | 24 | PW | VR | | 0-0 | 34-16-11 | D05635P | | 13 | | D04305P | 8 | | | ALL |
| 543Z | | | VR | | 0-0 | 34-16-11 | D05635P | | 12 | | D04305P | 10 | | | ALL |
| 563B | 24 | PW | WM | | 6-3 | 32-45-14 | D13366A | | B04 | | D04913P | 45 | | | 050-099, 150-199 |
| 563R | 24 | PW | WM | | 0-0 | 32-45-14 | D13366A | | A04 | | D04913P | 46 | | | 050-099, 150-199 |
| 563Z | | | WM | | 0-0 | 32-45-14 | D13366A | | C04 | | D04913P | 31 | | | 050-099, 150-199 |
| 564B | 24 | PW | WN | | 6-3 | 32-45-14 | D13366A | | B05 | | D04913P | 47 | | | 050-099, 150-199 |
| 564R | 24 | PW | WN | | 0-0 | 32-45-14 | D13366A | | A05 | | D04913P | 48 | | | 050-099, 150-199 |
| 564Z | | | WN | | 0-0 | 32-45-14 | D13366A | | C05 | | D04913P | 49 | | | 050-099, 150-199 |
| 565B | 24 | PW | WO | | 6-3 | 32-45-14 | D13366A | | B08 | | D04913P | 50 | | | 050-099, 150-199 |
| 565R | 24 | PW | WO | | 0-0 | 32-45-14 | D13366A | | A08 | | D04913P | 51 | | | 050-099, 150-199 |
| 565Z | | | WO | | 0-0 | 32-45-14 | D13366A | | C08 | | D04913P | 52 | | | 050-099, 150-199 |
| 566B | 24 | PW | WP | | 6-3 | 32-45-14 | D13366A | | B09 | | D04913P | 53 | | | 050-099, 150-199 |
| 566R | 24 | PW | WP | | 0-0 | 32-45-14 | D13366A | | A09 | | D04913P | 54 | | | 050-099, 150-199 |
| 566Z | | | WP | | 0-0 | 32-45-14 | D13366A | | C09 | | D04913P | 55 | | | 050-099, 150-199 |
| 605 | 24 | PK | | | 0-7 | 22-11-32 | D00421A | | B11 | | D00421A | B12 | | | 050-099 |
| 607 | 24 | PK | | | 2-5 | 22-11-32 | D00421A | | D04 | | D00421B | A04 | | | ALL |
| 620 | 24 | PK | | | 0-7 | 22-11-32 | D00421B | | B12 | | D00421B | D15 | | | 050-099 |
| 620 | 24 | PK | | | 2-5 | 22-11-32 | D00421B | | B12 | | D00421B | D15 | | | 150-199, 275-299 |
| 621 | 24 | PK | | | 0-7 | 22-11-32 | D00421B | | A12 | | D00421B | B15 | | | 050-099 |
| 621 | 24 | PK | | | 2-10 | 22-11-32 | D00421B | | A12 | | D00421B | B15 | | | 150-199, 275-299 |
| 628 | 24 | PK | | | 6-7 | 32-45-11 | D13366A | | A01 | | D04705P | 14 | | | 050-099, 150-199 |
| 629 | 24 | PK | | | 6-5 | 32-45-11 | D13366B | | A13 | | D04705P | 15 | | | 050-099, 150-199 |
| 630 | 22 | PA | | | 2-2 | 32-45-11 | D13366A | | B01 | | GDY0002 | D.. | 2 | | 050-099, 150-199 |
| 631 | 22 | PA | | | 2-2 | 32-45-11 | D13366A | | D01 | | GDY0002 | S.. | 2 | | 050-099, 150-199 |
| 632 | 24 | PK | | | 0-7 | 22-11-32 | D00421A | | C11 | | D00421A | C12 | | | ALL |
| 634 | 24 | PK | | | 0-7 | 22-11-32 | D00421B | | J02 | | D00421B | J04 | | | 050-099 |
| 634 | 24 | PK | | | 2-5 | 22-11-32 | D00421B | | J02 | | D00421B | J04 | | | 150-199, 275-299 |
| 680 | 22 | PA | | | 2-2 | 32-45-11 | D13366A | | D03 | | GDY0002 | S.. | 2 | | 050-099, 155-199 |
| 843 | 24 | PK | | | 4-2 | 34-21-31 | D05557P | | 5 | | D04913P | 20 | | | ALL |
| W0129 | 286T0129 | E1-5 SHELF C | | | | | | | | | | | | | |
| 006 | 24 | PK | | | 3-0 | 22-15-12 | D05627P | | 13 | | TB0119F | C127 | 2 | | ALL |
| 009 | 22 | PA | | | 4-0 | 22-11-22 | D05637P | | 1 | | TB0119F | A155 | 2 | | ALL |
| 057 | 24 | PK | | | 4-0 | 22-14-31 | D05627P | | 7 | | TB0119H | 148 | 2 | | ALL |
| 062 | 24 | PK | | | 3-0 | 22-14-21 | D05627P | | 8 | | TB0119F | A127 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0120

Page 21

Jan 21/2005



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0129 | 286T0129 | | | E1-5 SHELF C (continued) | | | | | | | | | | | | |
| 077 | 24 | | PK | 4-0 | 22-14-31 | D05627P | | 6 | | | | TB0119H | 49 | 2 | | ALL |
| 079 | 24 | | PK | 4-0 | 22-14-31 | D05627P | | 1 | | | | TB0119H | 57 | 2 | | ALL |
| 080 | 24 | | PK | 4-0 | 22-14-31 | D05627P | | 2 | | | | TB0119H | 51 | 2 | | ALL |
| 087 | 24 | | PK | 4-0 | 22-15-12 | D05627P | | 21 | | | | TB0119F | A150 | 2 | | ALL |
| 089 | 24 | | PK | 3-0 | 22-14-21 | D05627P | | 9 | | | | TB0119F | C126 | 2 | | ALL |
| 101 | 24 | | PK | 4-0 | 34-46-12 | D05627P | | 15 | | | | TB0119D | C014 | 2 | | 050-099, 275-278 |
| 101 | 24 | | PK | 3-0 | 34-46-12 | D05627P | | 15 | | | | TB0119D | C014 | 2 | | 150-199 |
| 221B | 24 | | PW | IU | 5-0 | 34-22-28 | D05629J | | 2 | | | TB0119F | C170 | 2 | | ALL |
| 221R | 24 | | PW | IU | 0-0 | 34-22-28 | D05629J | | 1 | | | TB0119F | A170 | 2 | | ALL |
| 221Z | | | | IU | 0-0 | 34-22-28 | D05629J | | 3 | | | GDY0011 | S.. | 2 | | ALL |
| 233B | 24 | | PW | JH | 4-0 | 22-15-11 | D05627P | | 11 | | | TB0119G | 154 | 2 | | ALL |
| 233R | 24 | | PW | JH | 0-0 | 22-15-11 | D05627P | | 10 | | | TB0119G | 153 | 2 | | ALL |
| 233Z | | | | JH | 0-0 | 22-15-11 | D05627P | | 12 | | | GDY0009 | S.. | 2 | | ALL |
| 234B | 24 | | PW | JI | 4-0 | 22-12-31 | D05627P | | 4 | | | TB0119F | C146 | 2 | | ALL |
| 234R | 24 | | PW | JI | 0-0 | 22-12-31 | D05627P | | 3 | | | TB0119F | A146 | 2 | | ALL |
| 234Z | | | | JI | 0-0 | 22-12-31 | D05627P | | 5 | | | GDY0008 | S.. | 2 | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0130 | 286T0130 | | | LH FWD CABIN NIGHT ILLUMINATION LIGHTS | | | | | | | | | | | |
| 001 | 22 | | PA | | 2-0 | 33-22-41 | D06274P | = 1 | | | L00593 | = P | C | * | ALL |
| 002 | 22 | | PA | | 4-0 | 33-22-41 | L00594 | = P | C | | L00593 | = P | C | * | ALL |
| 003 | 22 | | PA | | 4-0 | 33-22-41 | L00594 | = G | C | | L00593 | = G | C | * | ALL |
| 004 | 22 | | PA | | 2-0 | 33-22-41 | D06272J | = 1 | | | L00593 | = G | C | * | ALL |
| W0131 | 286T0131 | | | E2-1 SHELF | | | | | | | | | | | |
| 001 | 22 | | PA | | 1-9 | 22-22-21 | D00667A | J12 | | | D05547J | 2 | | | ALL |
| 002 | 22 | | PA | | 2-8 | 22-21-21 | D05547J | 1 | | | D01261A | H05 | | | ALL |
| 004 | 22 | | PA | | 2-8 | 22-21-21 | D01261A | F15 | | | D05483J | 17 | | | ALL |
| 005 | 22 | | PA | | 2-6 | 22-21-21 | D01261A | C02 | | | D01257A | G01 | | | ALL |
| 006 | 22 | | PA | | 2-6 | 22-21-21 | D01261A | A02 | | | D01257A | B08 | | | ALL |
| 007 | 22 | | PA | | 2-6 | 22-21-21 | D01261A | B05 | | | D01257A | C05 | | | ALL |
| 008 | 22 | | PA | | 2-6 | 22-21-21 | D01261A | A05 | | | D01257A | E03 | | | ALL |
| 009 | 22 | | PA | | 3-8 | 22-21-21 | D01261A | C01 | | | D01255A | G01 | | | ALL |
| 010 | 22 | | PA | | 3-8 | 22-21-21 | D01261A | A01 | | | D01255A | B08 | | | ALL |
| 011 | 22 | | PA | | 3-8 | 22-21-21 | D01261A | G04 | | | D01255A | E03 | | | ALL |
| 012 | 22 | | PA | | 5-0 | 22-21-21 | D01261A | G05 | | | D01255A | C05 | | | ALL |
| 013 | 22 | | PA | | 3-8 | 22-21-21 | D01261A | D04 | | | GDX0001 | D.. | 2 | | 050-099 |
| 014 | 22 | | PA | | 3-8 | 22-21-21 | D01261A | C04 | | | GDX0001 | D.. | 2 | | 050-099 |
| 015 | 22 | | PA | | 3-8 | 22-21-21 | D01261A | B04 | | | GDX0001 | D.. | 2 | | 050-099 |
| 016 | 22 | | PA | | 3-3 | 27-09-11 | D04945J | 1 | | | TB0141H | 15 | 2 | | ALL |
| 017 | 22 | | PA | | 4-8 | 27-09-11 | D01257B | K15 | | | TB0141H | 15 | 2 | | ALL |
| 018 | 22 | | PA | | 2-7 | 27-09-11 | D01255B | K15 | | | TB0141H | 15 | 2 | | ALL |
| 019 | 22 | | PA | | 2-8 | 27-09-11 | D04945J | 2 | | | D01255B | E15 | | | ALL |
| 021 | 22 | | PA | | 3-8 | 22-21-21 | D01261A | E04 | | | GDX0001 | D.. | 2 | | ALL |
| 022 | 22 | | PA | | 1-9 | 22-24-21 | D00667A | C11 | | | D05547J | 5 | | | ALL |
| 023 | 22 | | PA | | 1-9 | 22-24-21 | D00667A | A09 | | | D05547J | 6 | | | ALL |
| 024 | 22 | | PA | | 1-9 | 22-24-21 | D00667A | A06 | | | D05547J | 3 | | | ALL |
| 025 | 22 | | PA | | 1-9 | 27-41-21 | D00667A | B06 | | | D05547J | 4 | | | 150-154 |
| 026 | 22 | | PA | | 1-0 | 27-61-17 | D00833B | D03 | | | D00833B | D04 | | | ALL |
| 030 | 22 | | PA | | 1-0 | 27-61-17 | D00833B | D05 | | | D00833B | D06 | | | ALL |
| 031 | 22 | | PA | | 1-0 | 27-61-17 | D00833B | B05 | | | D00833B | B06 | | | ALL |
| 037 | 22 | | PA | | 1-0 | 27-61-13 | D00831A | D05 | | | D00831A | D06 | | | ALL |
| 038 | 22 | | PA | | 1-0 | 27-61-13 | D00831A | B05 | | | D00831A | B06 | | | ALL |
| 040 | 22 | | PA | | 1-0 | 27-61-18 | D00835B | D11 | | | D00835B | D12 | | | ALL |
| 044 | 22 | | PA | | 1-0 | 27-61-18 | D00835B | D13 | | | D00835B | D14 | | | ALL |
| 045 | 22 | | PA | | 1-0 | 27-61-18 | D00835B | B13 | | | D00835B | B14 | | | ALL |
| 046 | 22 | | PA | | 1-0 | 27-61-13 | D00831A | A08 | | | D00831A | C07 | | | ALL |
| 052 | 22 | | PA | | 4-5 | 27-09-12 | D01265A | D07 | | | TB0141H | 101 | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 1
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0131 | 286T0131 | | | E2-1 SHELF (continued) | | | | | | | | | | | | | |
| 053 | 22 | | PA | | 4-3 | 27-09-12 | D01261A | | H04 | | | | TB0141H | 101 | 2 | | ALL |
| 054 | 22 | | PA | | 3-7 | 27-09-12 | D00667A | | D06 | | | | TB0141H | 101 | 2 | | ALL |
| 055 | 22 | | PA | | 4-8 | 27-09-12 | D00835B | | D10 | | | | TB0141H | 101 | 2 | | ALL |
| 056 | 22 | | PA | | 4-8 | 27-09-12 | D00833B | | D02 | | | | TB0141H | 101 | 2 | | ALL |
| 057 | 22 | | PA | | 2-7 | 27-09-12 | D00831A | | D01 | | | | TB0141H | 101 | 2 | | ALL |
| 058 | 22 | | PA | | 4-4 | 27-09-12 | D05547J | | 7 | | | | TB0141H | 101 | 2 | | ALL |
| 059 | 22 | | PA | | 2-6 | 27-09-13 | D00835A | | J13 | | | | D05547J | 8 | | | ALL |
| 060 | 22 | | PA | | 2-6 | 27-09-13 | D00835A | | K13 | | | | D05547J | 9 | | | ALL |
| 063 | 22 | | PA | | 2-0 | 27-09-13 | D00831A | | K13 | | | | GDX0003 | D.. | 2 | | ALL |
| 065 | 22 | | PA | | 3-5 | 27-11-22 | D00667A | | A07 | | | | D05547J | 10 | | | ALL |
| 066 | 22 | | PA | | 3-5 | 27-11-22 | D00667A | | A08 | | | | D05547J | 11 | | | ALL |
| 067 | 22 | | PA | | 3-5 | 27-21-12 | D01265A | | D12 | | | | D05547J | 12 | | | ALL |
| 068 | 22 | | PA | | 2-8 | 27-21-22 | D01255A | | A08 | | | | D01265A | A01 | | | ALL |
| 069 | 22 | | PA | | 2-8 | 27-21-22 | D01255A | | G03 | | | | D01265A | D01 | | | ALL |
| 070 | 22 | | PA | | 4-1 | 27-21-22 | D01257A | | A08 | | | | D01265A | A02 | | | ALL |
| 071 | 22 | | PA | | 4-1 | 27-21-22 | D01257A | | G03 | | | | D01265A | D02 | | | ALL |
| 074 | 22 | | PQ | | 2-2 | 27-41-21 | D00667A | | C08 | | | | D05483J | 32 | | | ALL |
| 074Z | | | | CX | 0-0 | 27-41-21 | D00667A | | DED | | | | D05483J | DED | | | ALL |
| 075 | 22 | | PQ | | 2-2 | 27-41-21 | D00667A | | C07 | | | | D05483J | 33 | | | ALL |
| 075Z | | | | CY | 0-0 | 27-41-21 | D00667A | | DED | | | | D05483J | DED | | | ALL |
| 076 | 22 | | PA | | 3-7 | 27-41-21 | D00667A | | C09 | | | | TB0141G | 7 | 2 | | ALL |
| 077 | 22 | | PA | | 4-1 | 27-41-21 | D05483J | | 34 | | | | TB0141G | 7 | 2 | | ALL |
| 078 | 22 | | PA | | 4-1 | 27-41-21 | D05547J | | 28 | | | | TB0141G | 7 | 2 | | ALL |
| 079 | 22 | | PA | | 2-0 | 27-41-21 | D05547J | | 25 | | | | D00667A | D04 | | | ALL |
| 080 | 22 | | PA | | 2-0 | 27-41-21 | D05547J | | 26 | | | | D00667A | D05 | | | ALL |
| 081 | 22 | | PA | | 2-0 | 27-41-21 | D05547J | | 27 | | | | D00667A | C12 | | | ALL |
| 082 | 22 | | PA | | 3-9 | 27-41-21 | D00667A | | C04 | | | | D01255A | G02 | | | ALL |
| 083 | 22 | | PA | | 3-9 | 27-41-21 | D00667A | | C05 | | | | D01255A | A07 | | | ALL |
| 084 | 22 | | PA | | 3-9 | 27-41-21 | D00667A | | B04 | | | | D01255A | B05 | | | ALL |
| 085 | 22 | | PA | | 3-3 | 27-41-21 | D00667A | | A04 | | | | D01255A | E02 | | | ALL |
| 087 | 22 | | PA | | 3-3 | 27-41-21 | D00667A | | E04 | | | | D01257A | G02 | | | ALL |
| 088 | 22 | | PA | | 3-3 | 27-41-21 | D00667A | | E05 | | | | D01257A | A07 | | | ALL |
| 089 | 22 | | PA | | 3-3 | 27-41-21 | D00667A | | B05 | | | | D01257A | B05 | | | ALL |
| 090 | 22 | | PA | | 3-3 | 27-41-21 | D00667A | | A05 | | | | D01257A | E02 | | | ALL |
| 092 | 22 | | PA | | 3-7 | 27-61-11 | D05547J | | 29 | | | | TB0141G | 8 | 2 | | ALL |
| 093 | 22 | | PA | | 4-7 | 27-61-11 | D00835B | | E10 | | | | TB0141G | 8 | 2 | | ALL |
| 094 | 22 | | PA | | 4-7 | 27-61-11 | D00833B | | E02 | | | | TB0141G | 8 | 2 | | ALL |
| 095 | 22 | | PA | | 2-9 | 27-61-11 | D00831A | | E01 | | | | TB0141G | 8 | 2 | | ALL |
| 098 | 22 | | PA | | 2-6 | 27-61-13 | D01255A | | H01 | | | | D00831A | G03 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 2

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0131 | 286T0131 | | | E2-1 SHELF (continued) | | | | | | | | | | | |
| 099 | 22 | | PA | | 2-6 | 27-61-13 | D01255A | | C07 | | D00831A | | G05 | | ALL |
| 100 | 22 | | PA | | 4-0 | 22-21-21 | D01261B | | K10 | | TB0141H | 15 | 2 | | ALL |
| 101 | 22 | | PA | | 2-0 | 27-61-13 | D01255A | | A05 | | D00831A | | E11 | | ALL |
| 104 | 22 | | PA | | 4-2 | 27-61-13 | D00831A | | E12 | | D01257A | | A05 | | ALL |
| 105 | 22 | | PA | | 4-2 | 27-61-13 | D00831A | | F03 | | D01257A | | H01 | | ALL |
| 106 | 22 | | PA | | 4-2 | 27-61-13 | D00831A | | F05 | | D01257A | | C07 | | ALL |
| 107 | 22 | | PA | | 2-6 | 27-61-13 | D00831A | | K15 | | TB0141H | 15 | 2 | | ALL |
| 109 | 22 | | PA | | 2-8 | 27-61-17 | D01255A | | C08 | | D00833B | | G06 | | ALL |
| 110 | 22 | | PA | | 2-8 | 27-61-17 | D01255A | | H02 | | D00833B | | G04 | | ALL |
| 111 | 22 | | PA | | 3-1 | 27-61-17 | D00833A | | K15 | | TB0141H | 15 | 2 | | ALL |
| 112 | 22 | | PA | | 3-6 | 27-61-17 | D00833B | | F06 | | D01257A | | C08 | | ALL |
| 113 | 22 | | PA | | 3-6 | 27-61-17 | D00833B | | F04 | | D01257A | | H02 | | ALL |
| 114 | 22 | | PA | | 4-8 | 27-61-17 | D01255A | | C03 | | D01257A | | A03 | | ALL |
| 122 | 22 | | PA | | 3-6 | 27-61-18 | D00835B | | G14 | | D01255A | | B07 | | ALL |
| 123 | 22 | | PA | | 3-6 | 27-61-18 | D00835B | | G12 | | D01255A | | H03 | | ALL |
| 125 | 22 | | PA | | 3-6 | 27-61-18 | D00835B | | F14 | | D01257A | | B07 | | ALL |
| 126 | 22 | | PA | | 3-6 | 27-61-18 | D00835B | | F12 | | D01257A | | H03 | | ALL |
| 127 | 22 | | PA | | 4-6 | 27-61-18 | D00835A | | K15 | | TB0141H | 15 | 2 | | ALL |
| 129 | 22 | | PA | | 4-8 | 27-21-22 | D01257A | | A10 | | D01255A | | C10 | | ALL |
| 130 | 22 | | PA | | 5-3 | 27-21-22 | D01257A | | C12 | | TB0141H | 3 | 2 | | ALL |
| 133 | 22 | | PA | | 2-6 | 27-21-22 | D01265A | | C06 | | D05547J | 13 | | | ALL |
| 134 | 22 | | PA | | 2-6 | 27-21-22 | D01265A | | D15 | | D05547J | 22 | | | ALL |
| 135 | 22 | | PA | | 2-6 | 27-21-22 | D01265A | | A15 | | D05547J | 23 | | | ALL |
| 136 | 22 | | PA | | 2-6 | 27-21-22 | D01265A | | B15 | | D05547J | 24 | | | ALL |
| 137 | 22 | | PA | | 5-0 | 27-61-17 | D01257A | | C01 | | TB0141H | 112 | 2 | | ALL |
| 139 | 22 | | PA | | 2-4 | 27-61-17 | D00833B | | C02 | | D00667A | | A01 | | ALL |
| 188 | 22 | | PA | | 3-8 | 22-21-21 | D01261A | | C04 | | GDX0001 | D.. | 2 | | 150-199, 275-299 |
| 194 | 22 | | PA | | 3-8 | 22-21-21 | D01261A | | B04 | | GDX0001 | D.. | 2 | | 150-199, 275-299 |
| 195 | 22 | | PA | | 3-8 | 22-21-21 | D01261A | | A04 | | GDX0001 | D.. | 2 | | 150-199, 275-299 |
| 196 | 22 | | PA | | 2-6 | 22-21-21 | D01261A | | H15 | | D04983J | 3 | | | 150-199, 275-299 |
| 201 | 20 | | UA | | 0-18 | 22-21-21 | D05547J | | | FE | GDX0008 | S.. | 2 | | ALL |
| 201B | 24 | | PW | IA | 2-6 | 22-21-21 | D01261A | | K05 | | D05547J | 16 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 22-21-21 | D01261A | | K04 | | D05547J | 15 | | | ALL |
| 201Z | | | | IA | 0-0 | 22-21-21 | D01261A | | DED | | D05547J | | | FE | ALL |
| 202B | 22 | | PB | IB | 1-9 | 22-21-21 | D01261A | | D15 | | D05483J | 19 | | | ALL |
| 202R | 22 | | PB | IB | 0-0 | 22-21-21 | D01261A | | E14 | | D05483J | 18 | | | ALL |
| 203B | 22 | | PB | IC | 4-5 | 22-21-21 | D01261A | | E15 | | TB0141H | 3 | 2 | | ALL |
| 203R | 22 | | PB | IC | 0-0 | 22-21-21 | D01261A | | F14 | | TB0141H | 1 | 2 | | ALL |
| 204B | 22 | | PB | ID | 3-8 | 22-21-21 | TB0141H | | 3 | 2 | D05483J | 24 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0130
 Page 3
 Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|-------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0131 | 286T0131 | | | E2-1 SHELF (continued) | | | | | | | | | | | | | |
| 204R | 22 | PB | ID | 0-0 | 22-21-21 | TB0141H | | 1 | 2 | | | | D05483J | 23 | | | ALL |
| 205B | 24 | PW | IE | 4-5 | 22-21-21 | D01261A | | A15 | | | | | TB0141G | 6 | 2 | | ALL |
| 205R | 24 | PW | IE | 0-0 | 22-21-21 | D01261A | | A14 | | | | | TB0141G | 5 | 2 | | ALL |
| 205Z | | | IE | 0-0 | 22-21-21 | D01261A | | DED | | | | | TB0141G | | | FC | ALL |
| 206B | 24 | PW | IF | 3-9 | 27-11-22 | D00667A | | A12 | | | | | TB0141G | 6 | 2 | | ALL |
| 206R | 24 | PW | IF | 0-0 | 27-11-22 | D00667A | | A11 | | | | | TB0141G | 5 | 2 | | ALL |
| 206Z | | | IF | 0-0 | 27-11-22 | D00667A | | DED | | | | | TB0141G | | | FC | ALL |
| 207 | 20 | UA | | 0-18 | 27-11-22 | D05547J | | | | | FF | | GDX0008 | S.. | 2 | | ALL |
| 207B | 24 | PW | IG | 4-0 | 27-11-22 | D05547J | | | 19 | | | | TB0141G | 6 | 2 | | ALL |
| 207R | 24 | PW | IG | 0-0 | 27-11-22 | D05547J | | | 18 | | | | TB0141G | 5 | 2 | | ALL |
| 207Z | | | IG | 0-0 | 27-11-22 | D05547J | | | | | FF | | TB0141G | | | FC | ALL |
| 208B | 22 | PB | IH | 3-6 | 27-61-13 | D00831A | | J06 | | | | | TB0141H | 112 | 2 | | ALL |
| 208R | 22 | PB | IH | 0-0 | 27-61-13 | D00831A | | K06 | | | | | TB0141H | 110 | 2 | | ALL |
| 209B | 22 | PB | II | 3-6 | 27-61-13 | D05483J | | 3 | | | | | D00831A | G08 | | | ALL |
| 209R | 22 | PB | II | 0-0 | 27-61-13 | D05483J | | 1 | | | | | D00831A | G09 | | | ALL |
| 210B | 22 | PB | IJ | 3-6 | 27-61-13 | D05483J | | 15 | | | | | TB0141G | 109 | 2 | | ALL |
| 210R | 22 | PB | IJ | 0-0 | 27-61-13 | D05483J | | 14 | | | | | TB0141G | 108 | 2 | | ALL |
| 211B | 22 | PB | IK | 3-6 | 27-61-13 | D05483J | | 9 | | | | | TB0141G | 109 | 2 | | ALL |
| 211R | 22 | PB | IK | 0-0 | 27-61-13 | D05483J | | 8 | | | | | TB0141G | 108 | 2 | | ALL |
| 212B | 22 | PB | IL | 3-6 | 27-61-13 | D00831A | | G11 | | | | | D05483J | 11 | | | ALL |
| 212R | 22 | PB | IL | 0-0 | 27-61-13 | D00831A | | G10 | | | | | D05483J | 10 | | | ALL |
| 213B | 22 | PB | IM | 2-6 | 27-61-13 | D00831A | | J11 | | | | | TB0141G | 109 | 2 | | ALL |
| 213R | 22 | PB | IM | 0-0 | 27-61-13 | D00831A | | K11 | | | | | TB0141G | 108 | 2 | | ALL |
| 214B | 22 | PB | IN | 3-1 | 27-61-17 | D00833B | | J07 | | | | | TB0141H | 112 | 2 | | ALL |
| 214R | 22 | PB | IN | 0-0 | 27-61-17 | D00833B | | K07 | | | | | TB0141H | 110 | 2 | | ALL |
| 215B | 22 | PB | IO | 2-6 | 27-61-17 | D01255A | | C01 | | | | | TB0141H | 112 | 2 | | ALL |
| 215R | 22 | PB | IO | 0-0 | 27-61-17 | D01255A | | A01 | | | | | TB0141H | 110 | 2 | | ALL |
| 216B | 22 | PB | IP | 4-8 | 27-61-17 | D05137J | | 9 | | | | | TB0141H | 112 | 2 | | ALL |
| 216R | 22 | PB | IP | 0-0 | 27-61-17 | D05137J | | 8 | | | | | TB0141H | 110 | 2 | | ALL |
| 217B | 22 | PB | IQ | 4-8 | 27-61-17 | D05137J | | 2 | | | | | TB0141H | 112 | 2 | | ALL |
| 217R | 22 | PB | IQ | 0-0 | 27-61-17 | D05137J | | 1 | | | | | TB0141H | 110 | 2 | | ALL |
| 218B | 22 | PB | IR | 4-8 | 27-61-18 | D00835B | | J15 | | | | | TB0141H | 112 | 2 | | ALL |
| 218R | 22 | PB | IR | 0-0 | 27-61-18 | D00835B | | K15 | | | | | TB0141H | 110 | 2 | | ALL |
| 222B | 22 | PB | IV | 2-8 | 27-21-22 | D01255A | | C12 | | | | | TB0141H | 3 | 2 | | ALL |
| 222R | 22 | PB | IV | 0-0 | 27-21-22 | D01255A | | A12 | | | | | TB0141H | 1 | 2 | | ALL |
| 223B | 22 | PB | IW | 4-5 | 27-21-22 | D05483J | | 26 | | | | | TB0141H | 3 | 2 | | ALL |
| 223R | 22 | PB | IW | 0-0 | 27-21-22 | D05483J | | 25 | | | | | TB0141H | 1 | 2 | | ALL |
| 224B | 22 | PB | IX | 3-0 | 27-21-22 | D01265A | | A10 | | | | | TB0141H | 3 | 2 | | ALL |
| 224R | 22 | PB | IX | 0-0 | 27-21-22 | D01265A | | A09 | | | | | TB0141H | 1 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 4

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0131 | 286T0131 | | | E2-1 SHELF (continued) | | | | | | | | | | | |
| 225B | 22 | PB | IY | | 3-0 | 27-21-22 | D01265B | A05 | | | TB0141H | 3 | 2 | | ALL |
| 225R | 22 | PB | IY | | 0-0 | 27-21-22 | D01265B | A04 | | | TB0141H | 1 | 2 | | ALL |
| 226B | 22 | PB | JA | | 2-6 | 27-21-22 | D01265B | A10 | | | TB0141G | 104 | 2 | | ALL |
| 226R | 22 | PB | JA | | 0-0 | 27-21-22 | D01265B | A09 | | | TB0141G | 103 | 2 | | ALL |
| 227B | 22 | PB | JB | | 4-1 | 27-21-22 | D05483J | 31 | | | TB0141G | 104 | 2 | | ALL |
| 227R | 22 | PB | JB | | 0-0 | 27-21-22 | D05483J | 30 | | | TB0141G | 103 | 2 | | ALL |
| 228B | 22 | PB | JC | | 3-9 | 27-21-22 | D05547J | 35 | | | TB0141G | 104 | 2 | | ALL |
| 228R | 22 | PB | JC | | 0-0 | 27-21-22 | D05547J | 34 | | | TB0141G | 103 | 2 | | ALL |
| 229B | 22 | PB | JD | | 2-7 | 27-21-22 | D00667A | K05 | | | D01265A | D04 | | | ALL |
| 229R | 22 | PB | JD | | 0-0 | 27-21-22 | D00667A | K04 | | | D01265A | D05 | | | ALL |
| 230B | 22 | PB | JE | | 2-6 | 22-21-21 | D01261A | H12 | | | D04983J | 1 | | | 150-199, 275-299 |
| 230R | 22 | PB | JE | | 0-0 | 22-21-21 | D01261A | K12 | | | D04983J | 2 | | | 150-199, 275-299 |
| 231 | 20 | UA | | | 1-6 | 22-21-21 | D04983J | | | JF | GDX0008 | S.. | 2 | | 150-199, 275-299 |
| 231B | 22 | PR | JF | | 1-9 | 22-21-21 | D01261B | K15 | | | D04983J | 5 | | | 150-199, 275-299 |
| 231R | 22 | PR | JF | | 0-0 | 22-21-21 | D01261B | K14 | | | D04983J | 4 | | | 150-199, 275-299 |
| 231Z | | | JF | | 0-0 | 22-21-21 | D01261B | DED | | | D04983J | | | JF | 150-199, 275-299 |
| 301B | 22 | PC | MA | | 2-6 | 22-21-21 | D01261A | C14 | | | D05483J | 21 | | | ALL |
| 301R | 22 | PC | MA | | 0-0 | 22-21-21 | D01261A | D14 | | | D05483J | 20 | | | ALL |
| 301Y | 22 | PC | MA | | 0-0 | 22-21-21 | D01261A | C15 | | | D05483J | 22 | | | ALL |
| 302B | 22 | PC | MB | | 2-8 | 27-61-13 | D00831A | K05 | | | TB0141G | 13 | 2 | | ALL |
| 302R | 22 | PC | MB | | 0-0 | 27-61-13 | D00831A | K03 | | | TB0141G | 12 | 2 | | ALL |
| 302Y | 22 | PC | MB | | 0-0 | 27-61-13 | D00831A | K04 | | | TB0141G | 14 | 2 | | ALL |
| 303B | 22 | PC | MC | | 2-7 | 27-61-13 | D00831A | J05 | | | TB0141G | 10 | 2 | | ALL |
| 303R | 22 | PC | MC | | 0-0 | 27-61-13 | D00831A | J03 | | | TB0141G | 9 | 2 | | ALL |
| 303Y | 22 | PC | MC | | 0-0 | 27-61-13 | D00831A | J04 | | | TB0141G | 11 | 2 | | ALL |
| 304B | 22 | PC | MD | | 2-9 | 27-61-13 | D00831A | J10 | | | D05483J | 6 | | | ALL |
| 304R | 22 | PC | MD | | 0-0 | 27-61-13 | D00831A | J08 | | | D05483J | 12 | | | ALL |
| 304Y | 22 | PC | MD | | 0-0 | 27-61-13 | D00831A | J09 | | | D05483J | 13 | | | ALL |
| 305B | 22 | PC | ME | | 3-1 | 27-61-13 | D00831A | K10 | | | D05483J | 4 | | | ALL |
| 305R | 22 | PC | ME | | 0-0 | 27-61-13 | D00831A | K08 | | | D05483J | 5 | | | ALL |
| 305Y | 22 | PC | ME | | 0-0 | 27-61-13 | D00831A | K09 | | | D05483J | 7 | | | ALL |
| 306B | 22 | PC | MF | | 3-4 | 27-61-17 | D00833B | J06 | | | TB0141G | 10 | 2 | | ALL |
| 306R | 22 | PC | MF | | 0-0 | 27-61-17 | D00833B | J04 | | | TB0141G | 9 | 2 | | ALL |
| 306Y | 22 | PC | MF | | 0-0 | 27-61-17 | D00833B | J05 | | | TB0141G | 11 | 2 | | ALL |
| 307B | 22 | PC | MG | | 5-0 | 27-61-17 | D05137J | 4 | | | TB0141G | 10 | 2 | | ALL |
| 307R | 22 | PC | MG | | 0-0 | 27-61-17 | D05137J | 6 | | | TB0141G | 9 | 2 | | ALL |
| 307Y | 22 | PC | MG | | 0-0 | 27-61-17 | D05137J | 7 | | | TB0141G | 11 | 2 | | ALL |
| 308B | 22 | PC | MH | | 5-0 | 27-61-17 | D05137J | 10 | | | TB0141G | 13 | 2 | | ALL |
| 308R | 22 | PC | MH | | 0-0 | 27-61-17 | D05137J | 3 | | | TB0141G | 12 | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 5
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0131 | 286T0131 | | | E2-1 SHELF (continued) | | | | | | | | | | | | |
| 308Y | 22 | PC | MH | 0-0 | 27-61-17 | D05137J | | 5 | | | | TB0141G | 14 | 2 | ALL | |
| 309B | 22 | PC | MI | 3-0 | 27-61-17 | D00833B | | K06 | | | | TB0141G | 13 | 2 | ALL | |
| 309R | 22 | PC | MI | 0-0 | 27-61-17 | D00833B | | K04 | | | | TB0141G | 12 | 2 | ALL | |
| 309Y | 22 | PC | MI | 0-0 | 27-61-17 | D00833B | | K05 | | | | TB0141G | 14 | 2 | ALL | |
| 310B | 22 | PC | MJ | 3-1 | 27-61-18 | D00835B | | J14 | | | | TB0141G | 10 | 2 | ALL | |
| 310R | 22 | PC | MJ | 0-0 | 27-61-18 | D00835B | | J12 | | | | TB0141G | 9 | 2 | ALL | |
| 310Y | 22 | PC | MJ | 0-0 | 27-61-18 | D00835B | | J13 | | | | TB0141G | 11 | 2 | ALL | |
| 311B | 22 | PC | MK | 4-3 | 27-61-18 | D00835B | | K14 | | | | TB0141G | 13 | 2 | ALL | |
| 311R | 22 | PC | MK | 0-0 | 27-61-18 | D00835B | | K12 | | | | TB0141G | 12 | 2 | ALL | |
| 311Y | 22 | PC | MK | 0-0 | 27-61-18 | D00835B | | K13 | | | | TB0141G | 14 | 2 | ALL | |
| 312B | 22 | PC | ML | 4-1 | 27-21-22 | D05483J | | 28 | | | | TB0141G | 106 | 2 | ALL | |
| 312R | 22 | PC | ML | 0-0 | 27-21-22 | D05483J | | 27 | | | | TB0141G | 105 | 2 | ALL | |
| 312Y | 22 | PC | ML | 0-0 | 27-21-22 | D05483J | | 29 | | | | TB0141G | 107 | 2 | ALL | |
| 313B | 22 | PC | MM | 3-6 | 27-21-22 | D01265A | | B09 | | | | TB0141G | 106 | 2 | ALL | |
| 313R | 22 | PC | MM | 0-0 | 27-21-22 | D01265A | | B08 | | | | TB0141G | 105 | 2 | ALL | |
| 313Y | 22 | PC | MM | 0-0 | 27-21-22 | D01265A | | B10 | | | | TB0141G | 107 | 2 | ALL | |
| 314B | 22 | PC | MN | 3-6 | 27-21-22 | D01265B | | B05 | | | | TB0141G | 106 | 2 | ALL | |
| 314R | 22 | PC | MN | 0-0 | 27-21-22 | D01265B | | B06 | | | | TB0141G | 105 | 2 | ALL | |
| 314Y | 22 | PC | MN | 0-0 | 27-21-22 | D01265B | | B04 | | | | TB0141G | 107 | 2 | ALL | |
| 315B | 22 | PC | MO | 3-9 | 22-21-21 | D01261A | | K02 | | | | D01255A | K06 | | ALL | |
| 315R | 22 | PC | MO | 0-0 | 22-21-21 | D01261A | | K01 | | | | D01255A | K05 | | ALL | |
| 315Y | 22 | PC | MO | 0-0 | 22-21-21 | D01261A | | J01 | | | | D01255A | J05 | | ALL | |
| 316B | 22 | PC | MP | 3-9 | 22-21-21 | D01261A | | H01 | | | | D01255A | J06 | | ALL | |
| 316R | 22 | PC | MP | 0-0 | 22-21-21 | D01261A | | J02 | | | | D01255A | K07 | | ALL | |
| 316Y | 22 | PC | MP | 0-0 | 22-21-21 | D01261A | | H02 | | | | D01255A | J07 | | ALL | |
| 317B | 22 | PC | MQ | 3-9 | 22-21-21 | D01261A | | G02 | | | | D01257A | K06 | | ALL | |
| 317R | 22 | PC | MQ | 0-0 | 22-21-21 | D01261A | | G01 | | | | D01257A | K05 | | ALL | |
| 317Y | 22 | PC | MQ | 0-0 | 22-21-21 | D01261A | | F01 | | | | D01257A | J05 | | ALL | |
| 318B | 22 | PC | MR | 3-9 | 22-21-21 | D01261A | | E01 | | | | D01257A | J06 | | ALL | |
| 318R | 22 | PC | MR | 0-0 | 22-21-21 | D01261A | | F02 | | | | D01257A | K07 | | ALL | |
| 318Y | 22 | PC | MR | 0-0 | 22-21-21 | D01261A | | E02 | | | | D01257A | J07 | | ALL | |
| 319B | 22 | PC | MS | 3-5 | 27-41-21 | D00667A | | H05 | | | | D01255A | H06 | | ALL | |
| 319R | 22 | PC | MS | 0-0 | 27-41-21 | D00667A | | H04 | | | | D01255A | H05 | | ALL | |
| 319Y | 22 | PC | MS | 0-0 | 27-41-21 | D00667A | | H06 | | | | D01255A | G05 | | ALL | |
| 320B | 22 | PC | MT | 3-5 | 27-41-21 | D00667A | | J05 | | | | D01255A | G06 | | ALL | |
| 320R | 22 | PC | MT | 0-0 | 27-41-21 | D00667A | | J04 | | | | D01255A | H07 | | ALL | |
| 320Y | 22 | PC | MT | 0-0 | 27-41-21 | D00667A | | J06 | | | | D01255A | G07 | | ALL | |
| 321B | 22 | PC | MU | 3-5 | 27-41-21 | D00667A | | F05 | | | | D01257A | H06 | | ALL | |
| 321R | 22 | PC | MU | 0-0 | 27-41-21 | D00667A | | F04 | | | | D01257A | H05 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 6

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0131 | 286T0131 | | | E2-1 SHELF (continued) | | | | | | | | | | | |
| 321Y | 22 | PC | MU | | 0-0 | 27-41-21 | D00667A | F06 | | | D01257A | G05 | | | ALL |
| 322B | 22 | PC | MV | | 3-5 | 27-41-21 | D00667A | G05 | | | D01257A | G06 | | | ALL |
| 322R | 22 | PC | MV | | 0-0 | 27-41-21 | D00667A | G04 | | | D01257A | H07 | | | ALL |
| 322Y | 22 | PC | MV | | 0-0 | 27-41-21 | D00667A | G06 | | | D01257A | G07 | | | ALL |
| FRA | | | | | 0-0 | 22-21-21 | D04983J | | | JF | D04983J | 7 | | | 150-199, 275-299 |
| FRE | | | | | 0-0 | 22-21-21 | D05547J | | 17 | | D05547J | | | FE | ALL |
| FRF | | | | | 0-0 | 27-11-22 | D05547J | | 20 | | D05547J | | | FF | ALL |
| W0132 | 286T0132 | | | FWD RIGHT SIDE SCULPTURED CEILING PANEL | | | | | | | | | | | |
| 001 | 22 | PA | | | 4-0 | 33-21-21 | D06096P | = 1 | | | L00456 | = P | C | | 275-299 |
| 002 | 22 | PA | | | 4-0 | 33-21-21 | D06102J | = 1 | | | L00456 | = G | C | | 275-299 |
| 008 | 22 | PA | | | 2-0 | 33-26-21 | D06100P | 1 | | | L00399 | G | C | | 275-299 |
| 011 | 22 | PA | | | 2-0 | 33-26-21 | D06100P | 4 | | | L00399 | P | C | | 275-299 |
| 012 | 22 | PA | | | 2-0 | 33-26-21 | D06100P | 5 | | | L00399 | S | C | | 275-299 |
| 018 | 20 | PA | | | 4-0 | 33-21-11 | L00233 | = G | E | | D06098J | 1 | | | 275-299 |
| L-A | | | | | 0-0 | 33-21-11 | L00233 | BLK | | | D06098J | 4 | | | 275-299 |
| L-B | | | | | 0-0 | 33-21-11 | L00233 | BLK | | | D06098J | 5 | | | 275-299 |
| L-C | | | | | 0-0 | 33-21-11 | L00233 | WHT | | | D06098J | 2 | | | 275-299 |
| L-D | | | | | 0-0 | 33-21-11 | L00233 | WHT | | | D06098J | 3 | | | 275-299 |
| W0133 | 286T0133 | | | E2-2 L,SHELF | | | | | | | | | | | |
| 001 | 22 | PQ | AA | | 5-2 | 34-61-11 | D04217P | 5 | | | D00323C | 1 | | | 050-099 |
| 001 | 22 | PQ | AA | | 6-0 | 34-61-11 | D04217P | 5 | | | D00323C | 1 | | | 150-199, 275-299 |
| 001Z | | | AA | | 0-0 | 34-61-11 | D04217P | DED | | | D00323C | DED | | | ALL |
| 002 | 24 | PV | AB | | 3-10 | 34-61-11 | D04217P | 6 | | | D04429P | 7 | | | 050-099 |
| 002 | 24 | PV | AB | | 5-0 | 34-61-11 | D04217P | 6 | | | D04429P | 7 | | | 150-199, 275-299 |
| 002Z | | | AB | | 0-0 | 34-61-11 | D04217P | DED | | | D04429P | DED | | | ALL |
| 003 | 24 | PK | | | 3-5 | 34-61-11 | D04151P | 20 | | | D04429P | 10 | | | 050-099 |
| 003 | 24 | PK | | | 5-0 | 34-61-11 | D04151P | 20 | | | D04429P | 10 | | | 150-199, 275-299 |
| 007 | 20 | PA | | | 2-2 | 34-61-11 | D00323C | 7 | | | GDX0013 | A.. | 2 | | 050-099 |
| 007 | 20 | PA | | | 3-0 | 34-61-11 | D00323C | 7 | | | GDX0013 | A.. | 2 | | 150-199, 275-299 |
| 008 | 20 | PA | | | 2-2 | 34-61-11 | D00323C | 8 | | | GDX0013 | D.. | 2 | | 050-099 |
| 008 | 20 | PA | | | 3-0 | 34-61-11 | D00323C | 8 | | | GDX0013 | D.. | 2 | | 150-199, 275-299 |
| 010 | 24 | PV | AJ | | 3-4 | 34-61-13 | D00323A | K11 | | | TB0133F | A175 | 2 | | 050-099 |
| 010 | 24 | PV | AJ | | 4-0 | 34-61-13 | D00323A | K11 | | | TB0133F | A175 | 2 | | 150-199, 275-299 |
| 010Z | | | AJ | | 0-0 | 34-61-13 | D00323A | DED | | | TB0133F | DED | | | ALL |
| 011 | 22 | PA | | | 5-1 | 34-61-13 | D00323B | A13 | | | TB0133G | 28 | 2 | | 050-099 |
| 011 | 22 | PA | | | 4-0 | 34-61-13 | D00323B | A13 | | | TB0133G | 28 | 2 | | 150-199, 275-299 |
| 012 | 24 | PK | | | 5-7 | 34-61-13 | D00323A | K09 | | | TB0133G | 7 | 2 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 7
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | |
| 012 | 24 | | PK | 6-0 | 34-61-13 | D00323A | K09 | | | | TB0133G | 7 | 2 | | 150-199, 275-299 | |
| 013 | 24 | | PK | 3-10 | 34-61-14 | TB0133G | 87 | 2 | | | D04791P | 2 | | | 050-099 | |
| 013 | 24 | | PK | 6-0 | 34-61-14 | TB0133G | 87 | 2 | | | D04791P | 2 | | | 150-199, 275-299 | |
| 015 | 22 | | PA | 4-2 | 34-61-14 | D00323B | K05 | | | | GDX0004 | D.. | 2 | | 050-099 | |
| 015 | 22 | | PA | 5-0 | 34-61-14 | D00323B | K05 | | | | GDX0004 | D.. | 2 | | 150-199, 275-299 | |
| 016 | 22 | | PA | 2-6 | 34-61-14 | D00323B | K01 | | | | GDX0012 | D.. | 2 | | 050-099 | |
| 016 | 22 | | PA | 3-0 | 34-61-14 | D00323B | K01 | | | | GDX0012 | D.. | 2 | | 150-199, 275-299 | |
| 01B | 22 | | PA | 3-0 | 34-61-13 | D00323B | K11 | | | | GDX0012 | D.. | 2 | | 150-199 | |
| 022 | 24 | | PK | 3-5 | 34-61-23 | D05703J | 11 | | | | TB0133G | 7 | 2 | | 050-099 | |
| 022 | 24 | | PK | 4-0 | 34-61-23 | D05703J | 11 | | | | TB0133G | 7 | 2 | | 150-199, 275-299 | |
| 023 | 24 | | PK | 2-8 | 34-61-23 | D05703J | 18 | | | | TB0133G | 28 | 2 | | 050-099 | |
| 023 | 24 | | PK | 4-0 | 34-61-23 | D05703J | 18 | | | | TB0133G | 28 | 2 | | 150-199, 275-299 | |
| 026 | 22 | | PA | 2-8 | 34-22-17 | D04151P | 4 | | | | D05703J | 34 | | | 050-099 | |
| 026 | 22 | | PA | 4-0 | 34-22-17 | D04151P | 4 | | | | D05703J | 34 | | | 150-199, 275-299 | |
| 027 | 22 | | PQ | BB | 3-3 | 34-61-13 | D00323B | A15 | | | TB0133F | C180 | 2 | | 050-099 | |
| 027 | 22 | | PQ | BB | 4-0 | 34-61-13 | D00323B | A15 | | | TB0133F | C180 | 2 | | 150-199, 275-299 | |
| 027Z | | | | BB | 0-0 | 34-61-13 | D00323B | DED | | | TB0133F | DED | | | ALL | |
| 030 | 22 | | PA | 3-0 | 34-61-13 | D00323B | B15 | | | | GDX0012 | S.. | 2 | | 157, 167-199, 277-299 | |
| 030 | 22 | | PA | 4-0 | 34-61-13 | D00323B | B15 | | | | GDX0012 | S.. | 2 | | 275-276 | |
| 032 | 24 | | PV | BG | 4-6 | 34-61-13 | D00323B | B14 | | | D05203P | 21 | | | 050-099 | |
| 032 | 24 | | PV | BG | 5-0 | 34-61-13 | D00323B | B14 | | | D05203P | 21 | | | 150-199, 275-299 | |
| 032Z | | | | BG | 0-0 | 34-61-13 | D00323B | DED | | | D05203P | DED | | | ALL | |
| 033 | 24 | | PV | BH | 4-6 | 34-61-13 | D00323B | C14 | | | D05203P | 22 | | | 050-099 | |
| 033 | 24 | | PV | BH | 5-0 | 34-61-13 | D00323B | C14 | | | D05203P | 22 | | | 150-199, 275-299 | |
| 033Z | | | | BH | 0-0 | 34-61-13 | D00323B | DED | | | D05203P | DED | | | ALL | |
| 034 | 24 | | PV | BI | 4-6 | 34-61-13 | D00323B | F14 | | | D05203P | 23 | | | 050-099 | |
| 034 | 24 | | PV | BI | 5-0 | 34-61-13 | D00323B | F14 | | | D05203P | 23 | | | 150-199, 275-299 | |
| 034Z | | | | BI | 0-0 | 34-61-13 | D00323B | DED | | | D05203P | DED | | | ALL | |
| 035 | 24 | | PV | BJ | 4-6 | 34-61-13 | D00323B | G13 | | | D05203P | 24 | | | 050-099 | |
| 035 | 24 | | PV | BJ | 5-0 | 34-61-13 | D00323B | G13 | | | D05203P | 24 | | | 150-199, 275-299 | |
| 035Z | | | | BJ | 0-0 | 34-61-13 | D00323B | DED | | | D05203P | DED | | | ALL | |
| 036 | 24 | | PV | BK | 4-6 | 34-61-13 | D00323B | J14 | | | D05203P | 25 | | | 050-099 | |
| 036 | 24 | | PV | BK | 5-0 | 34-61-13 | D00323B | J14 | | | D05203P | 25 | | | 150-199, 275-299 | |
| 036Z | | | | BK | 0-0 | 34-61-13 | D00323B | DED | | | D05203P | DED | | | ALL | |
| 037 | 24 | | PK | 4-6 | 34-61-13 | D00323B | J13 | | | | D05203P | 26 | | | 050-099 | |
| 037 | 24 | | PK | 5-0 | 34-61-13 | D00323B | J13 | | | | D05203P | 26 | | | 150-199, 275-299 | |
| 038 | 24 | | PK | 4-6 | 34-61-13 | D00323B | A14 | | | | D05203P | 27 | | | 050-099 | |
| 038 | 24 | | PK | 5-0 | 34-61-13 | D00323B | A14 | | | | D05203P | 27 | | | 150-199, 275-299 | |
| 039 | 24 | | PK | 4-6 | 34-61-13 | D00323B | E13 | | | | D05203P | 28 | | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 8

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 039 | 24 | | PK | | 5-0 | 34-61-13 | D00323B | E13 | | | D05203P | 28 | | | 150-199, 275-299 |
| 040 | 24 | | PK | | 4-6 | 34-61-13 | D00323B | G14 | | | D05203P | 29 | | | 050-099 |
| 040 | 24 | | PK | | 5-0 | 34-61-13 | D00323B | G14 | | | D05203P | 29 | | | 150-199, 275-299 |
| 041 | 24 | | PK | | 4-6 | 34-61-13 | D00323B | F13 | | | D05203P | 30 | | | 050-099 |
| 041 | 24 | | PK | | 5-0 | 34-61-13 | D00323B | F13 | | | D05203P | 30 | | | 150-199, 275-299 |
| 043 | 22 | | PA | | 3-0 | 34-61-14 | D00323B | H11 | | | GDX0012 | D.. | 2 | | 150, 152-165, 167-199, 275-299 |
| 043 | 22 | | PA | | 3-0 | 34-61-14 | D00323B | D11 | | | GDX0012 | D.. | 2 | | 151, 166 |
| 048 | 24 | | PK | | 4-7 | 34-12-61 | D04151P | 37 | | | TB0133H | 89 | 2 | | 050-099 |
| 048 | 24 | | PK | | 6-0 | 34-12-61 | D04151P | 37 | | | TB0133H | 89 | 2 | | 150-199, 275-299 |
| 051 | 20 | | PQ | CA | 4-0 | 34-51-11 | D00329C | 2 | | | D04233P | 1 | | | 050-099 |
| 051 | 20 | | PQ | CA | 5-0 | 34-51-11 | D00329C | 2 | | | D04233P | 1 | | | 150-199, 275-299 |
| 051Z | | | | CA | 0-0 | 34-51-11 | D04233P | DED | | | D00329C | DED | | | ALL |
| 052 | 20 | | PA | | 2-5 | 34-51-11 | D00329C | 3 | | | GDX0007 | A.. | 2 | | 050-099 |
| 052 | 20 | | PA | | 3-0 | 34-51-11 | D00329C | 3 | | | GDX0007 | A.. | 2 | | 150-199, 275-299 |
| 053 | 20 | | PA | | 2-5 | 34-51-11 | D00329C | 4 | | | GDX0007 | S.. | 2 | | 050-099 |
| 053 | 20 | | PA | | 3-0 | 34-51-11 | D00329C | 4 | | | GDX0007 | S.. | 2 | | 150-199, 275-299 |
| 054 | 22 | | PA | | 3-1 | 34-51-11 | D00329B | A11 | | | TB0133G | 28 | 2 | | 050-099 |
| 054 | 22 | | PA | | 4-0 | 34-51-11 | D00329B | A11 | | | TB0133G | 28 | 2 | | 150-199, 275-299 |
| 055 | 24 | | PK | | 2-9 | 34-51-11 | D00329B | A15 | | | TB0133G | 31 | 2 | | 050-099 |
| 055 | 24 | | PK | | 4-0 | 34-51-11 | D00329B | A15 | | | TB0133G | 31 | 2 | | 150-199, 275-299 |
| 056 | 22 | | PA | | 4-4 | 34-51-11 | TB0133G | 28 | 2 | | D04373P | 6 | | | 050-099 |
| 056 | 22 | | PA | | 6-0 | 34-51-11 | TB0133G | 28 | 2 | | D04373P | 6 | | | 150-199, 275-299 |
| 057 | 24 | | PV | CG | 3-5 | 34-53-13 | D04217P | 15 | | | TB0133G | 114 | 2 | | 050-099 |
| 057 | 24 | | PV | CG | 4-0 | 34-53-13 | D04217P | 15 | | | TB0133G | 114 | 2 | | 150-199, 275-299 |
| 057Z | | | | CG | 0-0 | 34-53-13 | D04217P | DED | | | TB0133G | DED | | | ALL |
| 065 | 24 | | PK | | 4-2 | 34-21-11 | D04717P | 17 | | | TB0133H | 89 | 2 | | 050-099 |
| 065 | 24 | | PK | | 5-0 | 34-21-11 | D04717P | 17 | | | TB0133H | 89 | 2 | | 150-199, 275-299 |
| 068 | 24 | | PK | | 3-1 | 34-53-11 | D00331B | H03 | | | D04695P | 9 | | | 050-099 |
| 068 | 24 | | PK | | 4-0 | 34-53-11 | D00331B | H03 | | | D04695P | 9 | | | 150-156, 162-166, 275-276 |
| 070 | 24 | | PK | | 3-1 | 34-53-11 | D00331B | K03 | | | D04695P | 7 | | | 050-099 |
| 070 | 24 | | PK | | 4-0 | 34-53-11 | D00331B | K03 | | | D04695P | 7 | | | 150-199, 275-299 |
| 072 | 20 | | PA | | 2-6 | 34-53-11 | D00331C | 7 | | | GDX0003 | A.. | 2 | | ALL |
| 073 | 20 | | PA | | 2-6 | 34-53-11 | D00331C | 11 | | | GDX0003 | D.. | 2 | | ALL |
| 076 | 20 | | PQ | DA | 3-5 | 34-53-11 | D04217P | 9 | | | TB0133G | 116 | 2 | | 050-099 |
| 076 | 20 | | PQ | DA | 4-0 | 34-53-11 | D04217P | 9 | | | TB0133G | 116 | 2 | | 150-199, 275-299 |
| 076Z | | | | DA | 0-0 | 34-53-11 | D04217P | DED | | | TB0133G | DED | | | ALL |
| 077 | 22 | | PA | | 3-4 | 34-53-11 | D04695P | 3 | | | TB0133G | 116 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 9

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|--------|-------------|-----|---|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | | | | |
| 077 | 22 | | PA | | 4-0 | 34-53-11 | D04695P | | | | 3 | | | | TB0133G | 116 | 2 | | 150-199, 275-299 |
| 078 | 22 | | PA | | 3-3 | 34-53-11 | D00331C | | | | 1 | | | | TB0133G | 116 | 2 | | 050-099 |
| 078 | 22 | | PA | | 4-0 | 34-53-11 | D00331C | | | | 1 | | | | TB0133G | 116 | 2 | | 150-199, 275-299 |
| 079 | 24 | | PK | | 3-1 | 34-53-11 | D04695P | | | | 6 | | | | D00331A | G07 | | | 050-099 |
| 079 | 24 | | PK | | 4-0 | 34-53-11 | D04695P | | | | 6 | | | | D00331A | G07 | | | 150-199, 275-299 |
| 081 | 24 | | PK | | 3-1 | 34-53-11 | D04695P | | | | 8 | | | | D00331A | J05 | | | 050-099 |
| 081 | 24 | | PK | | 4-0 | 34-53-11 | D04695P | | | | 8 | | | | D00331A | J05 | | | 150-199, 275-299 |
| 082 | 24 | | PK | | 3-6 | 34-53-11 | D04791P | | | | 3 | | | | D04695P | 5 | | | 050-099 |
| 082 | 24 | | PK | | 4-0 | 34-53-11 | D04791P | | | | 3 | | | | D04695P | 5 | | | 150-154 |
| 082 | 24 | | PK | | 6-0 | 34-53-11 | D04695P | | | | 5 | | | | D04791P | 3 | | | 155-199 |
| 082 | 24 | | PK | | 5-0 | 34-53-11 | D04695P | | | | 5 | | | | D04791P | 3 | | | 275-299 |
| 084 | 24 | | PK | | 3-1 | 31-35-11 | D05753J | | | | 45 | | | | D01769A | A03 | | | 050-099 |
| 084 | 24 | | PK | | 4-0 | 31-35-11 | D05753J | | | | 45 | | | | D01769A | A03 | | | 150-199, 275-299 |
| 085 | 22 | | PQ | DJ | 3-5 | 34-55-11 | D00333C | | | | 1 | | | | D04217P | 10 | | | 050-099 |
| 085 | 22 | | PQ | DJ | 4-0 | 34-55-11 | D00333C | | | | 1 | | | | D04217P | 10 | | | 150-199, 275-299 |
| 085Z | | | | DJ | 0-0 | 34-55-11 | D04217P | | | DED | | | | | D00333C | DED | | | ALL |
| 086 | 20 | | PA | | 2-1 | 34-55-11 | D00333C | | | | 7 | | | | GDX0001 | A.. | 2 | | 050-099 |
| 086 | 20 | | PA | | 3-0 | 34-55-11 | D00333C | | | | 7 | | | | GDX0001 | A.. | 2 | | 150-199, 275-299 |
| 087 | 20 | | PA | | 2-1 | 34-55-11 | D00333C | | | | 11 | | | | GDX0001 | S.. | 2 | | 050-099 |
| 087 | 20 | | PA | | 3-0 | 34-55-11 | D00333C | | | | 11 | | | | GDX0001 | S.. | 2 | | 150-199, 275-299 |
| 088 | 24 | | PK | | 2-9 | 34-55-11 | D00333B | | | B05 | | | | | TB0133G | 7 | 2 | | 050-099 |
| 088 | 24 | | PK | | 4-0 | 34-55-11 | D00333B | | | B05 | | | | | TB0133G | 7 | 2 | | 150-199, 275-299 |
| 089 | 24 | | PK | | 3-9 | 34-55-11 | D00333B | | | K05 | | | | | TB0133G | 31 | 2 | | 050-099 |
| 089 | 24 | | PK | | 5-0 | 34-55-11 | D00333B | | | K05 | | | | | TB0133G | 31 | 2 | | 150-199, 275-299 |
| 090 | 24 | | PK | | 3-2 | 34-55-11 | TB0133G | | | | 31 | 2 | | | D04735P | 34 | | | 050-099 |
| 090 | 24 | | PK | | 4-0 | 34-55-11 | TB0133G | | | | 31 | 2 | | | D04735P | 34 | | | 150-199, 275-299 |
| 093 | 24 | | PK | | 5-0 | 34-55-11 | TB0133G | | | | 7 | 2 | | | D04373P | 7 | | | 050-099 |
| 093 | 24 | | PK | | 6-0 | 34-55-11 | TB0133G | | | | 7 | 2 | | | D04373P | 7 | | | 150-199, 275-299 |
| 098 | 24 | | PK | | 3-3 | 34-61-15 | D04151P | | | | 1 | | | | D04791P | 22 | | | 050-099 |
| 098 | 24 | | PK | | 5-0 | 34-61-15 | D04151P | | | | 1 | | | | D04791P | 22 | | | 150-199, 275-299 |
| 102 | 24 | | PK | | 2-8 | 31-31-12 | D05703J | | | | 52 | | | | D04151P | 39 | | | 050-099 |
| 102 | 24 | | PK | | 4-0 | 31-31-12 | D05703J | | | | 52 | | | | D04151P | 39 | | | 150-199, 275-299 |
| 111 | 24 | | PK | | 3-4 | 31-41-16 | D05733J | | | | 41 | | | | TB0133G | 27 | 2 | | 050-099 |
| 111 | 24 | | PK | | 5-0 | 31-41-16 | D05733J | | | | 41 | | | | TB0133G | 27 | 2 | | 150-199, 275-299 |
| 112 | 24 | | PK | | 3-6 | 31-51-33 | D05203P | | | | 15 | | | | TB0133G | 27 | 2 | | 050-099 |
| 112 | 24 | | PK | | 5-0 | 31-51-33 | D05203P | | | | 15 | | | | TB0133G | 27 | 2 | | 150-199, 275-299 |
| 151 | 24 | | PK | | 3-4 | 31-31-13 | D05733J | | | | 13 | | | | D04151P | 2 | | | 050-099 |
| 151 | 24 | | PK | | 4-0 | 31-31-13 | D05733J | | | | 13 | | | | D04151P | 2 | | | 150-199, 275-299 |
| 152 | 24 | | PK | | 3-4 | 31-31-13 | D05733J | | | | 14 | | | | D04151P | 3 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 10

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 152 | 24 | | PK | | 4-0 | 31-31-13 | D05733J | | 14 | | D04151P | | 3 | | 150-199, 275-299 |
| 153 | 22 | | PA | | 2-0 | 31-35-16 | D01735A | | A05 | | GDX0007 | | S.. | 2 | 050-099 |
| 153 | 22 | | PA | | 4-0 | 31-35-16 | D01735A | | A05 | | GDX0007 | | S.. | 2 | 150-199, 275-299 |
| 154 | 22 | | PA | | 2-0 | 31-35-16 | D01735A | | K05 | | GDX0007 | | S.. | 2 | 050-099 |
| 154 | 22 | | PA | | 4-0 | 31-35-16 | D01735A | | K05 | | GDX0007 | | S.. | 2 | 150-199, 275-299 |
| 159 | 24 | | PK | | 2-11 | 31-31-19 | D05703J | | 44 | | D04445P | | 24 | | 050-099 |
| 159 | 24 | | PK | | 3-0 | 31-31-19 | D05703J | | 44 | | D04445P | | 24 | | 150-199, 275-299 |
| 161 | 24 | | PK | | 3-3 | 34-61-14 | D00323A | | K01 | | TB0133G | | 87 | 2 | 050-099 |
| 161 | 24 | | PK | | 4-0 | 34-61-14 | D00323A | | K01 | | TB0133G | | 87 | 2 | 150-199, 275-299 |
| 162 | 24 | | PK | | 3-3 | 34-61-14 | D00323A | | F09 | | TB0133G | | 87 | 2 | 050-099 |
| 162 | 24 | | PK | | 4-0 | 34-61-14 | D00323A | | F09 | | TB0133G | | 87 | 2 | 150-199, 275-299 |
| 163 | 22 | | PA | | 2-6 | 34-61-13 | D00323B | | B13 | | GDX0012 | | D.. | 2 | 050-099 |
| 163 | 22 | | PA | | 3-0 | 34-61-13 | D00323B | | B13 | | GDX0012 | | D.. | 2 | 150-156, 162-199 |
| 163 | 22 | | PA | | 3-0 | 34-61-13 | D00323B | | B13 | | GDX0012 | | S.. | 2 | 157 |
| 164 | 22 | | PA | | 2-11 | 31-35-16 | D01735C | | 1 | | TB0133G | | 163 | 2 | 050-099 |
| 164 | 22 | | PA | | 4-0 | 31-35-16 | D01735C | | 1 | | TB0133G | | 163 | 2 | 150-199, 275-299 |
| 165 | 22 | | PA | | 4-6 | 34-32-11 | D04151P | | 5 | | TB0133G | | 185 | 2 | 050-099 |
| 165 | 22 | | PA | | 6-0 | 34-32-11 | D04151P | | 5 | | TB0133G | | 185 | 2 | 150-199, 275-299 |
| 166 | 22 | | PA | | 4-6 | 34-32-11 | D04151P | | 6 | | TB0133G | | 186 | 2 | 050-099 |
| 166 | 22 | | PA | | 6-0 | 34-32-11 | D04151P | | 6 | | TB0133G | | 186 | 2 | 150-199, 275-299 |
| 167 | 22 | | PA | | 4-6 | 34-32-11 | D04151P | | 7 | | TB0133G | | 187 | 2 | 050-099 |
| 167 | 22 | | PA | | 6-0 | 34-32-11 | D04151P | | 7 | | TB0133G | | 187 | 2 | 150-199, 275-299 |
| 168 | 22 | | PA | | 2-0 | 31-35-16 | D01735C | | 4 | | GDX0007 | | A.. | 2 | 050-099 |
| 168 | 22 | | PA | | 4-0 | 31-35-16 | D01735C | | 4 | | GDX0007 | | A.. | 2 | 150-199, 275-299 |
| 170 | 24 | | PK | | 2-6 | 31-35-16 | D01735A | | A09 | | TB0133X | | A148 | BJ | 050-099 |
| 170 | 24 | | PK | | 4-0 | 31-35-16 | D01735A | | A09 | | TB0133X | | A148 | BJ | 150-199, 275-299 |
| 171 | 24 | | PK | | 2-6 | 31-35-16 | D01735A | | A10 | | TB0133X | | B148 | BJ | 050-099 |
| 171 | 24 | | PK | | 4-0 | 31-35-16 | D01735A | | A10 | | TB0133X | | B148 | BJ | 150-199, 275-299 |
| 172 | 24 | | PK | | 2-6 | 31-35-16 | D01735A | | A12 | | TB0133X | | C148 | BJ | 050-099 |
| 172 | 24 | | PK | | 4-0 | 31-35-16 | D01735A | | A12 | | TB0133X | | C148 | BJ | 150-199, 275-299 |
| 173 | 24 | | PK | | 2-6 | 31-35-16 | D01735A | | G08 | | TB0133X | | D148 | BJ | 050-099 |
| 173 | 24 | | PK | | 4-0 | 31-35-16 | D01735A | | G08 | | TB0133X | | D148 | BJ | 150-199, 275-299 |
| 174 | 24 | | PK | | 2-8 | 31-35-16 | D01735A | | G09 | | TB0133X | | A149 | BJ | 050-099 |
| 174 | 24 | | PK | | 4-0 | 31-35-16 | D01735A | | G09 | | TB0133X | | A149 | BJ | 150-199, 275-299 |
| 175 | 22 | | PA | | 3-11 | 34-32-11 | D00329B | | A02 | | TB0133G | | 185 | 2 | 050-099 |
| 175 | 22 | | PA | | 4-0 | 34-32-11 | D00329B | | A02 | | TB0133G | | 185 | 2 | 150-199, 275-299 |
| 176 | 22 | | PA | | 3-11 | 34-32-11 | D00329B | | B02 | | TB0133G | | 186 | 2 | 050-099 |
| 176 | 22 | | PA | | 5-0 | 34-32-11 | D00329B | | B02 | | TB0133G | | 186 | 2 | 150-199, 275-299 |
| 177 | 22 | | PA | | 3-11 | 34-32-11 | D00329B | | C02 | | TB0133G | | 187 | 2 | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 11
Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | | |
| 177 | 22 | | PA | 4-0 | 34-32-11 | D00329B | | C02 | | | | | TB0133G | 187 | 2 | | 150-199, 275-299 |
| 178 | 24 | | PK | 3-1 | 31-31-18 | D05733J | | 15 | | | | | TB0133G | 185 | 2 | | 050-099 |
| 178 | 24 | | PK | 4-0 | 31-31-18 | D05733J | | 15 | | | | | TB0133G | 185 | 2 | | 150-199, 275-299 |
| 179 | 24 | | PK | 3-1 | 31-31-18 | D05733J | | 16 | | | | | TB0133G | 186 | 2 | | 050-099 |
| 179 | 24 | | PK | 4-0 | 31-31-18 | D05733J | | 16 | | | | | TB0133G | 186 | 2 | | 150-199, 275-299 |
| 180 | 24 | | PK | 3-1 | 31-31-18 | D05733J | | 17 | | | | | TB0133G | 187 | 2 | | 050-099 |
| 180 | 24 | | PK | 4-0 | 31-31-18 | D05733J | | 17 | | | | | TB0133G | 187 | 2 | | 150-199, 275-299 |
| 187 | 24 | | PK | 2-11 | 31-35-16 | D01735A | | D05 | | | | | D01769B | J04 | | | 050-099 |
| 187 | 24 | | PK | 4-0 | 31-35-16 | D01735A | | D05 | | | | | D01769B | J04 | | | 150-199, 275-299 |
| 188 | 24 | | PK | 2-11 | 31-35-16 | D01735A | | G05 | | | | | D01769B | K04 | | | 050-099 |
| 188 | 24 | | PK | 4-0 | 31-35-16 | D01735A | | G05 | | | | | D01769B | K04 | | | 150-199, 275-299 |
| 191 | 22 | | PA | 5-0 | 34-61-14 | D00323A | | K04 | | | | | D04735P | 55 | | | 050-099 |
| 191 | 22 | | PA | 6-0 | 34-61-14 | D00323A | | K04 | | | | | D04735P | 55 | | | 150-199, 275-299 |
| 192 | 24 | | PK | 2-8 | 31-35-16 | D01735A | | G12 | | | | | TB0133X | B149 | BJ | | 050-099 |
| 192 | 24 | | PK | 4-0 | 31-35-16 | D01735A | | G12 | | | | | TB0133X | B149 | BJ | | 150-199, 275-299 |
| 193 | 24 | | PK | 2-8 | 31-35-16 | D01735A | | K06 | | | | | TB0133X | C149 | BJ | | 050-099 |
| 193 | 24 | | PK | 4-0 | 31-35-16 | D01735A | | K06 | | | | | TB0133X | C149 | BJ | | 150-199, 275-299 |
| 194 | 22 | | PA | 2-4 | 34-61-13 | D00323B | | C13 | | | | | GDX0012 | S.. | 2 | | 275-299 |
| 195 | 24 | | PK | 2-8 | 31-35-16 | D01735A | | A06 | | | | | TB0133X | D149 | BJ | | 050-099 |
| 195 | 24 | | PK | 4-0 | 31-35-16 | D01735A | | A06 | | | | | TB0133X | D149 | BJ | | 150-199, 275-299 |
| 196 | 24 | | PK | 2-8 | 31-35-16 | D01735A | | A14 | | | | | TB0133X | A150 | BJ | | 050-099 |
| 196 | 24 | | PK | 4-0 | 31-35-16 | D01735A | | A14 | | | | | TB0133X | A150 | BJ | | 150-199, 275-299 |
| 197 | 24 | | PK | 2-8 | 31-35-16 | D01735A | | A15 | | | | | TB0133X | B150 | BJ | | 050-099 |
| 197 | 24 | | PK | 4-0 | 31-35-16 | D01735A | | A15 | | | | | TB0133X | B150 | BJ | | 150-199, 275-299 |
| 198 | 22 | | PA | 3-0 | 34-61-14 | D00323B | | G11 | | | | | GDX0012 | D.. | 2 | | 150, 152-165, 167-199, 275-299 |
| 198 | 22 | | PA | 3-0 | 34-61-14 | D00323B | | C15 | | | | | GDX0012 | D.. | 2 | | 151, 166 |
| 199 | 22 | | PA | 2-6 | 34-61-14 | D00323B | | J11 | | | | | GDX0012 | D.. | 2 | | 050-099 |
| 199 | 22 | | PA | 3-0 | 34-61-14 | D00323B | | J11 | | | | | GDX0012 | D.. | 2 | | 150-199, 275-299 |
| 201B | 24 | | PW IA | 3-3 | 34-61-11 | TB0133F | | C177 | 2 | | | | D00323B | H01 | | | 050-099 |
| 201B | 24 | | PW IA | 4-0 | 34-61-11 | TB0133F | | C177 | 2 | | | | D00323B | H01 | | | 150-199, 275-299 |
| 201R | 24 | | PW IA | 0-0 | 34-61-11 | TB0133F | | A177 | 2 | | | | D00323B | G01 | | | ALL |
| 201Z | | | IA | 0-0 | 34-61-11 | D00323B | | DED | | | | | GDY0012 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 201Z | | | IA | 0-0 | 34-61-11 | D00323B | | DED | | | | | GDY0013 | S.. | 2 | | 150-154 |
| 202 | 20 | | UA | 1-6 | 34-61-11 | D00323A | | REF | | | IB | | GDX0013 | S.. | 2 | | 050-099 |
| 202 | 20 | | UA | 3-0 | 34-61-11 | D00323A | | REF | | | IB | | GDX0013 | S.. | 2 | | 150-199, 275-299 |
| 202B | 24 | | PW IB | 4-4 | 34-61-11 | D05703J | | 6 | | | | | D00323A | B13 | | | 050-099 |
| 202B | 24 | | PW IB | 5-0 | 34-61-11 | D05703J | | 6 | | | | | D00323A | B13 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 12

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | | | |
| 202R | 24 | PW | IB | 0-0 | 34-61-11 | D05703J | | 5 | | | | | D00323A | A13 | | | | ALL |
| 202Z | | | IB | 0-0 | 34-61-11 | D05703J | | 7 | | | | | D00323A | REF | | IB | | ALL |
| 203B | 24 | PW | IC | 3-5 | 34-61-11 | D05703J | | 9 | | | | | TB0133Z | 62 | BJ | | | 050-099 |
| 203B | 24 | PW | IC | 5-0 | 34-61-11 | D05703J | | 9 | | | | | TB0133Z | 62 | BJ | | | 150-199 |
| 203B | 24 | PW | IC | 4-0 | 34-61-11 | D05703J | | 9 | | | | | TB0133Z | 62 | BJ | | | 275-299 |
| 203R | 24 | PW | IC | 0-0 | 34-61-11 | D05703J | | 8 | | | | | TB0133Z | 61 | BJ | | | ALL |
| 203Z | | | IC | 0-0 | 34-61-11 | D05703J | | 10 | | | | | GDY0010 | S.. | 2 | | | ALL |
| 204B | 24 | PW | ID | 3-6 | 34-61-11 | D04429P | | 9 | | | | | TB0133Z | 62 | BJ | | | 050-099 |
| 204B | 24 | PW | ID | 5-0 | 34-61-11 | D04429P | | 9 | | | | | TB0133Z | 62 | BJ | | | 150-199, 275-299 |
| 204R | 24 | PW | ID | 0-0 | 34-61-11 | D04429P | | 8 | | | | | TB0133Z | 61 | BJ | | | ALL |
| 204Z | | | ID | 0-0 | 34-61-11 | D04429P | | 4 | | | | | GDY0010 | S.. | 2 | | | ALL |
| 206B | 24 | PW | IF | 4-4 | 34-61-11 | TB0133F | | C037 | 2 | | | | D00323A | E11 | | | | 050-099 |
| 206B | 24 | PW | IF | 5-0 | 34-61-11 | TB0133F | | C037 | 2 | | | | D00323A | E11 | | | | 150-199, 275-299 |
| 206R | 24 | PW | IF | 0-0 | 34-61-11 | TB0133F | | A037 | 2 | | | | D00323A | D11 | | | | ALL |
| 206Z | | | IF | 0-0 | 34-61-11 | GDY0007 | | S.. | 2 | | | | D00323A | DED | | | | 050-099, 155-199, 275-299 |
| 206Z | | | IF | 0-0 | 34-61-11 | GDY0006 | | S.. | 2 | | | | D00323A | DED | | | | 150-154 |
| 207B | 24 | PW | IG | 3-10 | 34-61-11 | D00323A | | B09 | | | | | TB0133Z | 62 | BJ | | | 050-099 |
| 207B | 24 | PW | IG | 5-0 | 34-61-11 | D00323A | | B09 | | | | | TB0133Z | 62 | BJ | | | 150-199, 275-299 |
| 207R | 24 | PW | IG | 0-0 | 34-61-11 | D00323A | | A09 | | | | | TB0133Z | 61 | BJ | | | ALL |
| 207Z | | | IG | 0-0 | 34-61-11 | D00323A | | DED | | | | | GDY0010 | S.. | 2 | | | ALL |
| 209 | 20 | UA | | 1-6 | 34-61-12 | D00323A | | REF | | | II | | GDX0013 | S.. | 2 | | | 050-099 |
| 209 | 20 | UA | | 3-0 | 34-61-12 | D00323A | | REF | | | II | | GDX0013 | S.. | 2 | | | 150-199, 275-299 |
| 209B | 24 | PW | II | 5-0 | 34-61-12 | D04735P | | 26 | | | | | D00323A | H01 | | | | ALL |
| 209R | 24 | PW | II | 0-0 | 34-61-12 | D04735P | | 25 | | | | | D00323A | G01 | | | | ALL |
| 209Z | | | II | 0-0 | 34-61-12 | D04735P | | 27 | | | | | D00323A | REF | | II | | ALL |
| 210 | 20 | UA | | 1-6 | 34-61-12 | D00323A | | REF | | | | IJ | GDX0013 | S.. | 2 | | | 050-099 |
| 210 | 20 | UA | | 3-0 | 34-61-12 | D00323A | | REF | | | | IJ | GDX0013 | S.. | 2 | | | 150-199, 275-299 |
| 210B | 24 | PW | IJ | 5-0 | 34-61-12 | D04735P | | 29 | | | | | D00323A | H05 | | | | ALL |
| 210R | 24 | PW | IJ | 0-0 | 34-61-12 | D04735P | | 28 | | | | | D00323A | G05 | | | | ALL |
| 210Z | | | IJ | 0-0 | 34-61-12 | D04735P | | 30 | | | | | D00323A | REF | | IJ | | ALL |
| 212B | 24 | PW | IL | 4-1 | 34-61-12 | D04717P | | 8 | | | | | TB0133Z | 83 | BJ | | | 050-099 |
| 212B | 24 | PW | IL | 5-0 | 34-61-12 | D04717P | | 8 | | | | | TB0133Z | 83 | BJ | | | 150-199, 275-299 |
| 212R | 24 | PW | IL | 0-0 | 34-61-12 | D04717P | | 7 | | | | | TB0133Z | 82 | BJ | | | ALL |
| 212Z | | | IL | 0-0 | 34-61-12 | D04717P | | 9 | | | | | GDY0012 | S.. | 2 | | | 050-099, 155-199, 275-299 |
| 212Z | | | IL | 0-0 | 34-61-12 | D04717P | | 9 | | | | | GDY0013 | S.. | 2 | | | 150-154 |
| 213B | 24 | PW | IM | 3-10 | 34-61-12 | D00323A | | E07 | | | | | TB0133H | 65 | 2 | | | 050-099 |
| 213B | 24 | PW | IM | 5-0 | 34-61-12 | D00323A | | E07 | | | | | TB0133H | 65 | 2 | | | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 13
Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|---------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 213R | 24 | | PW | IM | 0-0 | 34-61-12 | D00323A | | D07 | | | TB0133H | 63 | 2 | ALL |
| 213Z | | | | IM | 0-0 | 34-61-12 | D00323A | | DED | | | GDY0010 | S.. | 2 | 050-099, 155-199, 275-299 |
| 213Z | | | | IM | 0-0 | 34-61-12 | D00323A | | DED | | | GDY0011 | S.. | 2 | 150-154 |
| 214B | 24 | | PW | IN | 4-7 | 34-61-12 | D00323A | | B01 | | | TB0133G | 30 | 2 | 050-099 |
| 214B | 24 | | PW | IN | 6-0 | 34-61-12 | D00323A | | B01 | | | TB0133G | 30 | 2 | 150-199, 275-299 |
| 214R | 24 | | PW | IN | 0-0 | 34-61-12 | D00323A | | A01 | | | TB0133G | 29 | 2 | ALL |
| 214Z | | | | IN | 0-0 | 34-61-12 | D00323A | | DED | | | GDY0006 | S.. | 2 | ALL |
| 215B | 24 | | PW | IO | 6-0 | 34-61-12 | D00323A | | E01 | | | TB0133G | 11 | 2 | ALL |
| 215R | 24 | | PW | IO | 0-0 | 34-61-12 | D00323A | | D01 | | | TB0133G | 10 | 2 | ALL |
| 215Z | | | | IO | 0-0 | 34-61-12 | D00323A | | DED | | | GDY0001 | S.. | 2 | 050-099, 152-199, 275-299 |
| 215Z | | | | IO | 0-0 | 34-61-12 | D00323A | | DED | | | GDY0002 | S.. | 2 | 150-151 |
| 216B | 24 | | PW | IP | 3-10 | 34-61-12 | D00323A | | E15 | | | TB0133G | 162 | 2 | 050-099 |
| 216B | 24 | | PW | IP | 5-0 | 34-61-12 | D00323A | | E15 | | | TB0133G | 162 | 2 | 150-199, 275-299 |
| 216R | 24 | | PW | IP | 0-0 | 34-61-12 | D00323A | | D15 | | | TB0133G | 161 | 2 | ALL |
| 216Z | | | | IP | 0-0 | 34-61-12 | D00323A | | DED | | | GDY0010 | S.. | 2 | ALL |
| 217B | 24 | | PW | IQ | 3-4 | 34-61-12 | D00323A | | B03 | | | TB0133Z | 83 | BJ | 050-099 |
| 217B | 24 | | PW | IQ | 5-0 | 34-61-12 | D00323A | | B03 | | | TB0133Z | 83 | BJ | 150-199, 275-299 |
| 217R | 24 | | PW | IQ | 0-0 | 34-61-12 | D00323A | | A03 | | | TB0133Z | 82 | BJ | ALL |
| 217Z | | | | IQ | 0-0 | 34-61-12 | D00323A | | DED | | | GDY0012 | S.. | 2 | 050-099, 155-199, 275-299 |
| 217Z | | | | IQ | 0-0 | 34-61-12 | D00323A | | DED | | | GDY0013 | S.. | 2 | 150-154 |
| 218B | 24 | | PW | IR | 3-7 | 34-61-13 | D00323B | | E01 | | | TB0133F | C171 | 2 | 050-099 |
| 218B | 24 | | PW | IR | 4-0 | 34-61-13 | D00323B | | E01 | | | TB0133F | C171 | 2 | 150-199, 275-299 |
| 218R | 24 | | PW | IR | 0-0 | 34-61-13 | D00323B | | D01 | | | TB0133F | A171 | 2 | ALL |
| 218Z | | | | IR | 0-0 | 34-61-13 | D00323B | | DED | | | GDY0011 | S.. | 2 | ALL |
| 219B | 24 | | PW | IS | 3-7 | 34-61-13 | D00323B | | H07 | | | TB0133F | C172 | 2 | 050-099 |
| 219B | 24 | | PW | IS | 4-0 | 34-61-13 | D00323B | | H07 | | | TB0133F | C172 | 2 | 150-199, 275-299 |
| 219R | 24 | | PW | IS | 0-0 | 34-61-13 | D00323B | | G07 | | | TB0133F | A172 | 2 | ALL |
| 219Z | | | | IS | 0-0 | 34-61-13 | D00323B | | DED | | | GDY0011 | S.. | 2 | 050-099, 155-199, 275-299 |
| 219Z | | | | IS | 0-0 | 34-61-13 | D00323B | | DED | | | GDY0012 | S.. | 2 | 150-154 |
| 220B | 24 | | PW | IT | 3-3 | 34-61-13 | D00323B | | E05 | | | TB0133F | C173 | 2 | 050-099 |
| 220B | 24 | | PW | IT | 4-0 | 34-61-13 | D00323B | | E05 | | | TB0133F | C173 | 2 | 150-199, 275-299 |
| 220R | 24 | | PW | IT | 0-0 | 34-61-13 | D00323B | | D05 | | | TB0133F | A173 | 2 | ALL |
| 220Z | | | | IT | 0-0 | 34-61-13 | D00323B | | DED | | | GDY0011 | S.. | 2 | 050-099, 155-199, 275-299 |
| 220Z | | | | IT | 0-0 | 34-61-13 | D00323B | | DED | | | GDY0012 | S.. | 2 | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 14

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 221B | 24 | PW | IU | 3-3 | 34-61-13 | D00323B | B03 | | | TB0133F | C174 | 2 | | 050-099 | |
| 221B | 24 | PW | IU | 4-0 | 34-61-13 | D00323B | B03 | | | TB0133F | C174 | 2 | | 150-199, 275-299 | |
| 221R | 24 | PW | IU | 0-0 | 34-61-13 | D00323B | A03 | | | TB0133F | A174 | 2 | | ALL | |
| 221Z | | | IU | 0-0 | 34-61-13 | D00323B | DED | | | GDY0011 | S.. | 2 | | 050-099, 155-199, 275-299 | |
| 221Z | | | IU | 0-0 | 34-61-13 | D00323B | DED | | | GDY0012 | S.. | 2 | | 150-154 | |
| 222 | 20 | UA | | 1-6 | 34-61-14 | GDX0013 | S.. | 2 | | D00323A | REF | | IV | 050-099 | |
| 222 | 20 | UA | | 3-0 | 34-61-14 | GDX0013 | S.. | 2 | | D00323A | REF | | IV | 150-199, 275-299 | |
| 222B | 24 | PW | IV | 3-5 | 34-61-14 | D05733J | 30 | | | D00323A | H03 | | | 050-099 | |
| 222B | 24 | PW | IV | 5-0 | 34-61-14 | D05733J | 30 | | | D00323A | H03 | | | 150-199, 275-299 | |
| 222R | 24 | PW | IV | 0-0 | 34-61-14 | D05733J | 29 | | | D00323A | G03 | | | ALL | |
| 222Z | | | IV | 0-0 | 34-61-14 | D05733J | 31 | | | D00323A | REF | | IV | ALL | |
| 225 | 20 | UA | | 1-6 | 34-61-14 | D00323A | REF | | IY | GDX0013 | S.. | 2 | | 050-099 | |
| 225 | 20 | UA | | 3-0 | 34-61-14 | D00323A | REF | | IY | GDX0013 | S.. | 2 | | 150-199, 275-299 | |
| 225B | 24 | PW | IY | 4-4 | 34-61-14 | D00323A | E05 | | | D05703J | 47 | | | 050-099 | |
| 225B | 24 | PW | IY | 5-0 | 34-61-14 | D00323A | E05 | | | D05703J | 47 | | | 150-199, 275-299 | |
| 225R | 24 | PW | IY | 0-0 | 34-61-14 | D00323A | D05 | | | D05703J | 46 | | | ALL | |
| 225Z | | | IY | 0-0 | 34-61-14 | D00323A | REF | | IY | D05703J | 48 | | | ALL | |
| 226 | 20 | UA | | 1-6 | 34-61-14 | D00323A | REF | | JA | GDX0013 | S.. | 2 | | 050-099 | |
| 226 | 20 | UA | | 3-0 | 34-61-14 | D00323A | REF | | JA | GDX0013 | S.. | 2 | | 150-199, 275-299 | |
| 226B | 24 | PW | JA | 5-0 | 34-61-14 | D00323A | H07 | | | D04735P | 32 | | | ALL | |
| 226R | 24 | PW | JA | 0-0 | 34-61-14 | D00323A | G07 | | | D04735P | 31 | | | ALL | |
| 226Z | | | JA | 0-0 | 34-61-14 | D00323A | REF | | JA | D04735P | 33 | | | ALL | |
| 227 | 20 | UA | | 1-6 | 34-61-14 | D00323A | REF | | JB | GDX0013 | S.. | 2 | | 050-099 | |
| 227 | 20 | UA | | 3-0 | 34-61-14 | D00323A | REF | | JB | GDX0013 | S.. | 2 | | 150-199, 275-299 | |
| 227B | 24 | PW | JB | 4-8 | 34-61-14 | D00323A | B05 | | | D05201P | 23 | | | 050-099 | |
| 227B | 24 | PW | JB | 5-0 | 34-61-14 | D00323A | B05 | | | D05201P | 23 | | | 150-199, 275-299 | |
| 227R | 24 | PW | JB | 0-0 | 34-61-14 | D00323A | A05 | | | D05201P | 22 | | | ALL | |
| 227Z | | | JB | 0-0 | 34-61-14 | D00323A | REF | | JB | D05201P | 24 | | | ALL | |
| 229B | 22 | PB | JD | 2-8 | 34-12-21 | D04151P | 30 | | | D05703J | 54 | | | 050-099 | |
| 229B | 22 | PB | JD | 4-0 | 34-12-21 | D04151P | 30 | | | D05703J | 54 | | | 150-199, 275-299 | |
| 229R | 22 | PB | JD | 0-0 | 34-12-21 | D04151P | 29 | | | D05703J | 55 | | | ALL | |
| 230B | 24 | PW | JE | 3-3 | 34-61-14 | D00323B | E03 | | | TB0133G | 76 | 2 | | 050-099 | |
| 230B | 24 | PW | JE | 4-0 | 34-61-14 | D00323B | E03 | | | TB0133G | 76 | 2 | | 150-199, 275-299 | |
| 230R | 24 | PW | JE | 0-0 | 34-61-14 | D00323B | D03 | | | TB0133G | 75 | 2 | | ALL | |
| 230Z | | | JE | 0-0 | 34-61-14 | D00323B | DED | | | GDY0011 | S.. | 2 | | 050-099, 155-199, 275-299 | |
| 230Z | | | JE | 0-0 | 34-61-14 | D00323B | DED | | | GDY0012 | S.. | 2 | | 150-154 | |
| 232B | 24 | PW | JG | 3-6 | 34-61-16 | D02279 | B3 | | | TB0133H | 35 | 2 | | 050-099 | |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 15
Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 232B | 24 | PW | JG | 6-0 | 34-61-16 | D02279 | | B3 | | TB0133H | 35 | 2 | | 150-199, 275-299 | |
| 232R | 24 | PW | JG | 0-0 | 34-61-16 | D02279 | | A3 | | TB0133H | 33 | 2 | | ALL | |
| 232Z | | | JG | 0-0 | 34-61-16 | D02279 | | DED | | GDY0006 | S.. | 2 | | ALL | |
| 233B | 24 | PW | JH | 3-11 | 34-61-15 | D00323B | | E07 | | TB0133H | 190 | 2 | | 050-099 | |
| 233B | 24 | PW | JH | 4-0 | 34-61-15 | D00323B | | E07 | | TB0133H | 190 | 2 | | 150-199, 275-299 | |
| 233R | 24 | PW | JH | 0-0 | 34-61-15 | D00323B | | D07 | | TB0133H | 188 | 2 | | ALL | |
| 233Z | | | JH | 0-0 | 34-61-15 | D00323B | | DED | | GDY0013 | S.. | 2 | | ALL | |
| 234B | 24 | PW | JI | 4-7 | 34-61-15 | D00323A | | H09 | | TB0133H | 35 | 2 | | 050-099 | |
| 234B | 24 | PW | JI | 6-0 | 34-61-15 | D00323A | | H09 | | TB0133H | 35 | 2 | | 150-199, 275-299 | |
| 234R | 24 | PW | JI | 0-0 | 34-61-15 | D00323A | | G09 | | TB0133H | 33 | 2 | | ALL | |
| 234Z | | | JI | 0-0 | 34-61-15 | D00323A | | DED | | GDY0006 | S.. | 2 | | ALL | |
| 235B | 24 | PW | JJ | 2-6 | 34-61-23 | D05703J | | 13 | | TB0133G | 30 | 2 | | 050-099 | |
| 235B | 24 | PW | JJ | 4-0 | 34-61-23 | D05703J | | 13 | | TB0133G | 30 | 2 | | 150-199, 275-299 | |
| 235R | 24 | PW | JJ | 0-0 | 34-61-23 | D05703J | | 12 | | TB0133G | 29 | 2 | | ALL | |
| 235Z | | | JJ | 0-0 | 34-61-23 | D05703J | | 14 | | GDY0006 | S.. | 2 | | ALL | |
| 236B | 24 | PW | JK | 3-3 | 34-61-23 | D05703J | | 16 | | TB0133G | 11 | 2 | | 050-099 | |
| 236B | 24 | PW | JK | 4-0 | 34-61-23 | D05703J | | 16 | | TB0133G | 11 | 2 | | 150-199, 275-299 | |
| 236R | 24 | PW | JK | 0-0 | 34-61-23 | D05703J | | 15 | | TB0133G | 10 | 2 | | ALL | |
| 236Z | | | JK | 0-0 | 34-61-23 | D05703J | | 17 | | GDY0001 | S.. | 2 | | 050-099, 152-199, 275-299 | |
| 236Z | | | JK | 0-0 | 34-61-23 | D05703J | | 17 | | GDY0002 | S.. | 2 | | 150-151 | |
| 237B | 24 | PW | JL | 3-5 | 34-61-23 | D05703J | | 20 | | TB0133H | 65 | 2 | | 050-099 | |
| 237B | 24 | PW | JL | 5-0 | 34-61-23 | D05703J | | 20 | | TB0133H | 65 | 2 | | 150-199, 275-299 | |
| 237R | 24 | PW | JL | 0-0 | 34-61-23 | D05703J | | 19 | | TB0133H | 63 | 2 | | ALL | |
| 237Z | | | JL | 0-0 | 34-61-23 | D05703J | | 21 | | GDY0010 | S.. | 2 | | 050-099, 155-199, 275-299 | |
| 237Z | | | JL | 0-0 | 34-61-23 | D05703J | | 21 | | GDY0011 | S.. | 2 | | 150-154 | |
| 238B | 24 | PW | JM | 3-10 | 34-61-23 | D05703J | | 23 | | TB0133Z | 83 | BJ | | 050-099 | |
| 238B | 24 | PW | JM | 5-0 | 34-61-23 | D05703J | | 23 | | TB0133Z | 83 | BJ | | 150-199, 275-299 | |
| 238R | 24 | PW | JM | 0-0 | 34-61-23 | D05703J | | 22 | | TB0133Z | 82 | BJ | | ALL | |
| 238Z | | | JM | 0-0 | 34-61-23 | D05703J | | 24 | | GDY0012 | S.. | 2 | | 050-099, 155-199, 275-299 | |
| 238Z | | | JM | 0-0 | 34-61-23 | D05703J | | 24 | | GDY0013 | S.. | 2 | | 150-154 | |
| 240B | 24 | PW | JO | 4-0 | 34-61-12 | D04735P | | 52 | | TB0133H | 65 | 2 | | 050-099 | |
| 240B | 24 | PW | JO | 5-0 | 34-61-12 | D04735P | | 52 | | TB0133H | 65 | 2 | | 150-199, 275-299 | |
| 240R | 24 | PW | JO | 0-0 | 34-61-12 | D04735P | | 51 | | TB0133H | 63 | 2 | | ALL | |
| 240Z | | | JO | 0-0 | 34-61-12 | D04735P | | 53 | | GDY0010 | S.. | 2 | | 050-099, 155-199, 275-299 | |
| 240Z | | | JO | 0-0 | 34-61-12 | D04735P | | 53 | | GDY0011 | S.. | 2 | | 150-154 | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 16

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 241B | 24 | PW | JP | 3-1 | 22-32-11 | D04735P | | 23 | | TB0133Y | C130 | BJ | | 050-099 | |
| 241B | 24 | PW | JP | 4-0 | 22-32-11 | D04735P | | 23 | | TB0133Y | C130 | BJ | | 150-199, 275-299 | |
| 241R | 24 | PW | JP | 0-0 | 22-32-11 | D04735P | | 22 | | TB0133Y | A130 | BJ | | ALL | |
| 241Z | | | JP | 0-0 | 22-32-11 | D04735P | | 24 | | GDY0006 | S.. | 2 | | ALL | |
| 242B | 24 | PW | JQ | 4-3 | 22-41-11 | D05201P | | 11 | | TB0133H | 190 | 2 | | 050-099 | |
| 242B | 24 | PW | JQ | 5-0 | 22-41-11 | D05201P | | 11 | | TB0133H | 190 | 2 | | 150-199, 275-299 | |
| 242R | 24 | PW | JQ | 0-0 | 22-41-11 | D05201P | | 10 | | TB0133H | 188 | 2 | | ALL | |
| 242Z | | | JQ | 0-0 | 22-41-11 | D05201P | | 12 | | GDY0013 | S.. | 2 | | ALL | |
| 243B | 24 | PW | JR | 4-1 | 34-12-12 | D04735P | | 17 | | TB0133H | 71 | 2 | | 050-099 | |
| 243B | 24 | PW | JR | 5-0 | 34-12-12 | D04735P | | 17 | | TB0133H | 71 | 2 | | 150-199, 275-299 | |
| 243R | 24 | PW | JR | 0-0 | 34-12-12 | D04735P | | 16 | | TB0133H | 69 | 2 | | ALL | |
| 243Z | | | JR | 0-0 | 34-12-12 | D04735P | | 18 | | GDY0011 | S.. | 2 | | ALL | |
| 244B | 24 | PW | JS | 3-2 | 34-21-11 | D04717P | | 5 | | TB0133H | 35 | 2 | | 050-099 | |
| 244B | 24 | PW | JS | 4-0 | 34-21-11 | D04717P | | 5 | | TB0133H | 35 | 2 | | 150-199, 275-299 | |
| 244R | 24 | PW | JS | 0-0 | 34-21-11 | D04717P | | 4 | | TB0133H | 33 | 2 | | ALL | |
| 244Z | | | JS | 0-0 | 34-21-11 | D04717P | | 6 | | GDY0006 | S.. | 2 | | ALL | |
| 245B | 24 | PW | JT | 4-2 | 34-22-18 | D05201P | | 14 | | TB0133Z | 81 | BJ | | 050-099 | |
| 245B | 24 | PW | JT | 5-0 | 34-22-18 | D05201P | | 14 | | TB0133Z | 81 | BJ | | 150-199, 275-299 | |
| 245R | 24 | PW | JT | 0-0 | 34-22-18 | D05201P | | 13 | | TB0133Z | 80 | BJ | | ALL | |
| 245Z | | | JT | 0-0 | 34-22-18 | D05201P | | 15 | | GDY0012 | S.. | 2 | | ALL | |
| 247B | 24 | PW | JV | 4-2 | 34-61-15 | D04717P | | 22 | | TB0133H | 190 | 2 | | 050-099 | |
| 247B | 24 | PW | JV | 5-0 | 34-61-15 | D04717P | | 22 | | TB0133H | 190 | 2 | | 150-199, 275-299 | |
| 247R | 24 | PW | JV | 0-0 | 34-61-15 | D04717P | | 21 | | TB0133H | 188 | 2 | | ALL | |
| 247Z | | | JV | 0-0 | 34-61-15 | D04717P | | 23 | | GDY0013 | S.. | 2 | | ALL | |
| 249B | 24 | PW | JX | 3-10 | 31-25-11 | D05703J | | 32 | | TB0133G | 76 | 2 | | 050-099 | |
| 249B | 24 | PW | JX | 5-0 | 31-25-11 | D05703J | | 32 | | TB0133G | 76 | 2 | | 150-199, 275-299 | |
| 249R | 24 | PW | JX | 0-0 | 31-25-11 | D05703J | | 31 | | TB0133G | 75 | 2 | | ALL | |
| 249Z | | | JX | 0-0 | 31-25-11 | D05703J | | 33 | | GDY0011 | S.. | 2 | | 050-099, 155-199, 275-299 | |
| 249Z | | | JX | 0-0 | 31-25-11 | D05703J | | 33 | | GDY0012 | S.. | 2 | | 150-154 | |
| 250B | 24 | PW | JY | 4-6 | 31-25-11 | D04151P | | 14 | | TB0133G | 76 | 2 | | 050-099 | |
| 250B | 24 | PW | JY | 6-0 | 31-25-11 | D04151P | | 14 | | TB0133G | 76 | 2 | | 150-199, 275-299 | |
| 250R | 24 | PW | JY | 0-0 | 31-25-11 | D04151P | | 13 | | TB0133G | 75 | 2 | | ALL | |
| 250Z | | | JY | 0-0 | 31-25-11 | D04151P | | 15 | | GDY0011 | S.. | 2 | | 050-099, 155-199, 275-299 | |
| 250Z | | | JY | 0-0 | 31-25-11 | D04151P | | 15 | | GDY0012 | S.. | 2 | | 150-154 | |
| 255B | 24 | PW | KE | 3-1 | 34-61-15 | D05733J | | 2 | | TB0133H | 190 | 2 | | 050-099 | |
| 255B | 24 | PW | KE | 5-0 | 34-61-15 | D05733J | | 2 | | TB0133H | 190 | 2 | | 150-199, 275-299 | |
| 255R | 24 | PW | KE | 0-0 | 34-61-15 | D05733J | | 1 | | TB0133H | 188 | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 17

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | | |
| 255Z | | | | KE | 0-0 | 34-61-15 | D05733J | | 3 | | | | GDY0013 | S.. | 2 | | ALL |
| 257B | 24 | PW | | KG | 3-6 | 34-46-11 | D01769B | | D12 | | | | TB0133Y | C129 | BJ | | 050-099 |
| 257B | 24 | PW | | KG | 5-0 | 34-46-11 | D01769B | | D12 | | | | TB0133Y | C129 | BJ | | 150-199, 275-299 |
| 257R | 24 | PW | | KG | 0-0 | 34-46-11 | D01769B | | C12 | | | | TB0133Y | A129 | BJ | | ALL |
| 257Z | | | | KG | 0-0 | 34-46-11 | D01769B | | DED | | | | GDY0006 | S.. | 2 | | ALL |
| 258 | 20 | UA | | | 1-6 | 34-61-14 | D00323B | | REF | | KH | | GDY0013 | S.. | 2 | | 157, 167-199, 275-299 |
| 258B | 24 | PW | | KH | 3-0 | 34-61-14 | D00323B | | B05 | | | | D06199J | 4 | | | 157, 167-199, 277-299 |
| 258B | 24 | PW | | KH | 6-0 | 34-61-14 | D00323B | | B05 | | | | D06199J | 4 | | | 275-276 |
| 258R | 24 | PW | | KH | 0-0 | 34-61-14 | D00323B | | A05 | | | | D06199J | 3 | | | 157, 167-199, 275-299 |
| 258Z | | | | KH | 0-0 | 34-61-14 | D00323B | | REF | | KH | | D06199J | 5 | | | 157, 167-199, 275-299 |
| 259B | 24 | PW | | KI | 6-0 | 34-61-15 | D00323B | | H09 | ** | | | TB0133Y | C003 | BJ | | 157 |
| 259B | 24 | PW | | KI | 6-0 | 34-61-15 | D00323B | | REF | ** | | | TB0133Y | C003 | BJ | | 167-199 |
| 259B | 24 | PW | | KI | 8-0 | 34-61-15 | D00323B | | H09 | | | | TB0133Y | C003 | BJ | | 275-276 |
| 259B | 24 | PW | | KI | 6-0 | 34-61-15 | D00323B | | H09 | | | | TB0133Y | C003 | BJ | | 277-299 |
| 259R | 24 | PW | | KI | 0-0 | 34-61-15 | D00323B | | G09 | ** | | | TB0133Y | A003 | BJ | | 157 |
| 259R | 24 | PW | | KI | 0-0 | 34-61-15 | D00323B | | REF | ** | | | TB0133Y | A003 | BJ | | 167-199 |
| 259R | 24 | PW | | KI | 0-0 | 34-61-15 | D00323B | | G09 | | | | TB0133Y | A003 | BJ | | 275-299 |
| 259Z | | | | KI | 0-0 | 34-61-15 | D00323B | | DED | | | | GDY0001 | S.. | 2 | | 157, 167-199, 275-299 |
| 260 | 20 | UA | | | 1-6 | 31-35-11 | D01769A | | REF | | KJ | | GDY0010 | S.. | 2 | | ALL |
| 260B | 24 | PW | | KJ | 3-1 | 31-35-11 | D05753J | | 54 | | | | D01769A | B09 | | | 050-099 |
| 260B | 24 | PW | | KJ | 4-0 | 31-35-11 | D05753J | | 54 | | | | D01769A | B09 | | | 150-199, 275-299 |
| 260R | 24 | PW | | KJ | 0-0 | 31-35-11 | D05753J | | 53 | | | | D01769A | A09 | | | ALL |
| 260Z | | | | KJ | 0-0 | 31-35-11 | D05753J | | 55 | | | | D01769A | REF | | KJ | ALL |
| 261B | 24 | PW | | KK | 2-9 | 34-51-11 | D00329B | | B04 | | | | TB0133G | 30 | 2 | | 050-099 |
| 261B | 24 | PW | | KK | 5-0 | 34-51-11 | D00329B | | B04 | | | | TB0133G | 30 | 2 | | 150-199, 275-299 |
| 261R | 24 | PW | | KK | 0-0 | 34-51-11 | D00329B | | A04 | | | | TB0133G | 29 | 2 | | ALL |
| 261Z | | | | KK | 0-0 | 34-51-11 | D00329B | | DED | | | | GDY0006 | S.. | 2 | | ALL |
| 262 | 20 | UA | | | 1-6 | 34-51-11 | D00329B | | REF | | KL | | GDY0007 | S.. | 2 | | ALL |
| 262B | 24 | PW | | KL | 3-10 | 34-51-11 | D00329B | | C11 | | | | D04373P | 31 | | | 050-099 |
| 262B | 24 | PW | | KL | 4-0 | 34-51-11 | D00329B | | C11 | | | | D04373P | 31 | | | 150-199, 275-299 |
| 262R | 24 | PW | | KL | 0-0 | 34-51-11 | D00329B | | B11 | | | | D04373P | 18 | | | ALL |
| 262Z | | | | KL | 0-0 | 34-51-11 | D00329B | | REF | | KL | | D04373P | 30 | | | ALL |
| 263B | 22 | PB | | KM | 3-10 | 34-51-11 | D00329B | | D15 | | | | D04373P | 2 | | | 050-099 |
| 263B | 22 | PB | | KM | 4-0 | 34-51-11 | D00329B | | D15 | | | | D04373P | 2 | | | 150-199, 275-299 |
| 263R | 22 | PB | | KM | 0-0 | 34-51-11 | D00329B | | C15 | | | | D04373P | 1 | | | ALL |
| 264B | 24 | PW | | KN | 3-1 | 34-51-11 | D00329B | | C09 | | | | TB0133G | 23 | 2 | | 050-099 |
| 264B | 24 | PW | | KN | 4-0 | 34-51-11 | D00329B | | C09 | | | | TB0133Z | 23 | BJ | | 150-199, 275-299 |
| 264R | 24 | PW | | KN | 0-0 | 34-51-11 | D00329B | | B09 | | | | TB0133G | 24 | 2 | | 050-099 |
| 264R | 24 | PW | | KN | 0-0 | 34-51-11 | D00329B | | B09 | | | | TB0133Z | 24 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 18

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | |
| 264Z | | | | KN | 0-0 | 34-51-11 | D00329B | DED | | | | GDY0003 | S.. | 2 | | 050-099, 162-199, 275-299 |
| 264Z | | | | KN | 0-0 | 34-51-11 | D00329B | DED | | | | GDY0002 | S.. | 2 | | 150-157 |
| 265B | 24 | PL | | KO | 3-2 | 23-51-12 | D00329B | C07 | | | | D04735P | | 4 | | 050-099 |
| 265B | 24 | PL | | KO | 4-0 | 23-51-12 | D00329B | C07 | | | | D04735P | | 4 | | 150-199, 275-299 |
| 265R | 24 | PL | | KO | 0-0 | 23-51-12 | D00329B | B07 | | | | D04735P | | 2 | | ALL |
| 266B | 24 | PL | | KP | 3-2 | 23-51-12 | D00329B | D04 | | | | D04735P | | 3 | | 050-099 |
| 266B | 24 | PL | | KP | 4-0 | 23-51-12 | D00329B | D04 | | | | D04735P | | 3 | | 150-199, 275-299 |
| 266R | 24 | PL | | KP | 0-0 | 23-51-12 | D00329B | C04 | | | | D04735P | | 1 | | ALL |
| 267B | 24 | PW | | KQ | 3-2 | 34-22-19 | D00329B | C13 | | | | TB0133G | 153 | 2 | | 050-099 |
| 267B | 24 | PW | | KQ | 4-0 | 34-22-19 | D00329B | C13 | | | | TB0133G | 153 | 2 | | 150-199, 275-276 |
| 267R | 24 | PW | | KQ | 0-0 | 34-22-19 | D00329B | B13 | | | | TB0133G | 152 | 2 | | 050-099, 150-199, 275-276 |
| 267Z | | | | KQ | 0-0 | 34-22-19 | D00329B | DED | | | | GDY0009 | S.. | 2 | | 050-099, 155-199, 275-276 |
| 267Z | | | | KQ | 0-0 | 34-22-19 | D00329B | DED | | | | GDY0008 | S.. | 2 | | 150-154 |
| 268B | 24 | PW | | KR | 4-4 | 34-51-11 | D04373P | 22 | | | | D04735P | | 13 | | 050-099 |
| 268B | 24 | PW | | KR | 5-0 | 34-51-11 | D04373P | 22 | | | | D04735P | | 13 | | 150-199, 275-299 |
| 268R | 24 | PW | | KR | 0-0 | 34-51-11 | D04373P | 10 | | | | D04735P | | 14 | | ALL |
| 268Z | | | | KR | 0-0 | 34-51-11 | D04373P | 23 | | | | D04735P | | 15 | | ALL |
| 269B | 24 | PW | | KS | 3-11 | 34-51-11 | TB0133G | 30 | 2 | | | D04373P | | 21 | | 050-099 |
| 269B | 24 | PW | | KS | 5-0 | 34-51-11 | TB0133G | 30 | 2 | | | D04373P | | 21 | | 150-199, 275-299 |
| 269R | 24 | PW | | KS | 0-0 | 34-51-11 | TB0133G | 29 | 2 | | | D04373P | | 8 | | ALL |
| 269Z | | | | KS | 0-0 | 34-51-11 | GDY0006 | S.. | 2 | | | D04373P | | 20 | | ALL |
| 270 | 20 | UA | | | 1-6 | 31-35-11 | D01769A | REF | | | KT | GDY0010 | S.. | 2 | | 150-154 |
| 270B | 24 | PW | | KT | 4-5 | 31-35-11 | TB0133Z | 18 | BJ | | | D01769A | | H13 | | 050-099 |
| 270B | 24 | PW | | KT | 4-0 | 31-35-11 | TB0133Z | 18 | BJ | | | D01769A | | H13 | | 150-154 |
| 270B | 24 | PW | | KT | 5-0 | 31-35-11 | TB0133Z | 18 | BJ | | | D01769A | | H13 | | 155-199 |
| 270B | 24 | PW | | KT | 6-0 | 31-35-11 | TB0133Z | 18 | BJ | | | D01769A | | H13 | | 275-299 |
| 270R | 24 | PW | | KT | 0-0 | 31-35-11 | TB0133Z | 17 | BJ | | | D01769A | | G13 | | ALL |
| 270Z | | | | KT | 0-0 | 31-35-11 | GDY0002 | S.. | 2 | | | D01769A | | DED | | 050-099, 155-199, 275-299 |
| 270Z | | | | KT | 0-0 | 31-35-11 | D05753J | 24 | | | | D01769A | | REF | | 150-154 |
| 271 | 20 | UA | | | 1-6 | 31-35-11 | TB0133X | REF | | | KU | GDY0008 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 271B | 24 | PW | | KU | 2-9 | 31-35-11 | D01769B | H11 | | | | TB0133X | B159 | BJ | | 050-099 |
| 271B | 24 | PW | | KU | 4-0 | 31-35-11 | D01769B | H11 | | | | TB0133X | B159 | BJ | | 150-199, 275-299 |
| 271R | 24 | PW | | KU | 0-0 | 31-35-11 | D01769B | G11 | | | | TB0133X | A159 | BJ | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 19
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | | |
| 271Z | | | | KU | 0-0 | 31-35-11 | D01769B | DED | | | | | TB0133X | REF | | KU | 050-099, 155-199, 275-299 |
| 271Z | | | | KU | 0-0 | 31-35-11 | D01769B | DED | | | | | GDY0010 | S.. | 2 | | 150-154 |
| 273 | 20 | UA | | | 1-6 | 31-35-11 | D01769B | REF | | | KW | | GDY0010 | S.. | 2 | | ALL |
| 273B | 24 | PW | KW | | 3-3 | 31-35-11 | D05703J | 26 | | | | | D01769B | F15 | | | 050-099 |
| 273B | 24 | PW | KW | | 5-0 | 31-35-11 | D05703J | 26 | | | | | D01769B | F15 | | | 150-199, 275-299 |
| 273R | 24 | PW | KW | | 0-0 | 31-35-11 | D05703J | 25 | | | | | D01769B | E15 | | | ALL |
| 273Z | | | | KW | 0-0 | 31-35-11 | D05703J | 27 | | | | | D01769B | REF | | KW | ALL |
| 274B | 24 | PW | KX | | 3-5 | 31-31-20 | D04445P | 13 | | | | | D05753J | 20 | | | 050-099 |
| 274B | 24 | PW | KX | | 5-0 | 31-31-20 | D04445P | 13 | | | | | D05753J | 20 | | | 150-199, 275-299 |
| 274R | 24 | PW | KX | | 0-0 | 31-31-20 | D04445P | 12 | | | | | D05753J | 19 | | | ALL |
| 274Z | | | | KX | 0-0 | 31-31-20 | D04445P | 14 | | | | | D05753J | 21 | | | ALL |
| 275 | 20 | UA | | | 1-6 | 34-53-11 | D00331A | REF | | | KY | | GDY0003 | S.. | 2 | | 050-099 |
| 275 | 20 | UA | | | 2-6 | 34-53-11 | D00331A | REF | | | KY | | GDY0003 | S.. | 2 | | 150-199, 275-299 |
| 275B | 24 | PW | KY | | 3-1 | 34-53-11 | D00331A | F07 | | | | | D04695P | 11 | | | 050-099 |
| 275B | 24 | PW | KY | | 4-0 | 34-53-11 | D00331A | F07 | | | | | D04695P | 11 | | | 150-199, 275-299 |
| 275R | 24 | PW | KY | | 0-0 | 34-53-11 | D00331A | E07 | | | | | D04695P | 10 | | | ALL |
| 275Z | | | | KY | 0-0 | 34-53-11 | D00331A | REF | | | KY | | D04695P | 12 | | | ALL |
| 276 | 20 | UA | | | 2-6 | SPARE | D00331B | REF | | | LA | | GDY0003 | S.. | # | | 150-154 |
| 276B | 24 | PW | LA | | 4-0 | SPARE | D00331B | CAP | Y | | | | D04151P | 24 | | | 150-154 |
| 276R | 24 | PW | LA | | 0-0 | SPARE | D00331B | CAP | Y | | | | D04151P | 23 | | | 150-154 |
| 276Z | | | | LA | 0-0 | SPARE | D00331B | REF | | | LA | | D04151P | 25 | | | 150-154 |
| 277 | 20 | UA | | | 2-6 | SPARE | D00331B | REF | | | LB | | GDY0003 | S.. | # | | 150-154 |
| 277B | 24 | PW | LB | | 4-0 | SPARE | D00331B | CAP | Y | | | | D04151P | 9 | | | 150-154 |
| 277R | 24 | PW | LB | | 0-0 | SPARE | D00331B | CAP | Y | | | | D04151P | 8 | | | 150-154 |
| 277Z | | | | LB | 0-0 | SPARE | D00331B | REF | | | LB | | D04151P | 10 | | | 150-154 |
| 278B | 24 | PW | LC | | 4-3 | 34-53-11 | D00331A | J07 | | | | | TB0133H | 71 | 2 | | 050-099 |
| 278B | 24 | PW | LC | | 5-0 | 34-53-11 | D00331A | J07 | | | | | TB0133H | 71 | 2 | | 150-199, 275-299 |
| 278R | 24 | PW | LC | | 0-0 | 34-53-11 | D00331A | H07 | | | | | TB0133H | 69 | 2 | | ALL |
| 278Z | | | | LC | 0-0 | 34-53-11 | D00331A | DED | | | | | GDY0011 | S.. | 2 | | ALL |
| 279 | 20 | UA | | | 1-6 | 34-53-11 | D00331B | REF | | | LD | | GDY0003 | S.. | 2 | | 050-099 |
| 279 | 20 | UA | | | 2-6 | 34-53-11 | D00331B | REF | | | LD | | GDY0003 | S.. | 2 | | 150-199, 275-299 |
| 279B | 24 | PW | LD | | 2-10 | 34-53-11 | D00331B | B05 | | | | | D05703J | 2 | | | 050-099 |
| 279B | 24 | PW | LD | | 3-0 | 34-53-11 | D00331B | B05 | | | | | D05703J | 2 | | | 150-199, 275-299 |
| 279R | 24 | PW | LD | | 0-0 | 34-53-11 | D00331B | A05 | | | | | D05703J | 1 | | | ALL |
| 279Z | | | | LD | 0-0 | 34-53-11 | D00331B | REF | | | LD | | D05703J | 3 | | | ALL |
| 280B | 24 | PW | LE | | 4-0 | 34-51-11 | D00329B | C13 | | | | | TB0133G | 153 | 2 | | 277-299 |
| 280R | 24 | PW | LE | | 0-0 | 34-51-11 | D00329B | B13 | | | | | TB0133G | 152 | 2 | | 277-299 |
| 280Z | | | | LE | 0-0 | 34-51-11 | D00329B | DED | | | | | GDY0009 | S.. | 2 | | 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 20

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 281B | 24 | PW | LF | | 4-5 | 34-55-11 | D00333B | | H03 | | TB0133G | 155 | 2 | | 050-099 |
| 281B | 24 | PW | LF | | 5-0 | 34-55-11 | D00333B | | H03 | | TB0133G | 155 | 2 | | 150-156, 162-166 |
| 281B | 24 | PW | LF | | 5-0 | 34-55-11 | D00333B | | H03 | | TB0133Z | 155 | BJ | | 157, 167-199, 275-299 |
| 281R | 24 | PW | LF | | 0-0 | 34-55-11 | D00333B | | G03 | | TB0133G | 154 | 2 | | 050-099, 150-156, 162-166 |
| 281R | 24 | PW | LF | | 0-0 | 34-55-11 | D00333B | | G03 | | TB0133Z | 154 | BJ | | 157, 167-199, 275-299 |
| 281Z | | | LF | | 0-0 | 34-55-11 | D00333B | | DED | | GDY0009 | S.. | 2 | | ALL |
| 283B | 24 | PW | LH | | 3-4 | 34-61-15 | TB0133Z | 81 | BJ | | D00323A | B11 | | | 050-099 |
| 283B | 24 | PW | LH | | 4-0 | 34-61-15 | TB0133Z | 81 | BJ | | D00323A | B11 | | | 150-199, 275-299 |
| 283R | 24 | PW | LH | | 0-0 | 34-61-15 | TB0133Z | 80 | BJ | | D00323A | A11 | | | ALL |
| 283Z | | | LH | | 0-0 | 34-61-15 | GDY0012 | S.. | 2 | | D00323A | DED | | | ALL |
| 284B | 24 | PW | LI | | 3-5 | 31-31-14 | D05753J | 14 | | | TB0133Z | 81 | BJ | | 050-099 |
| 284B | 24 | PW | LI | | 5-0 | 31-31-14 | D05753J | 14 | | | TB0133Z | 81 | BJ | | 150-199, 275-299 |
| 284R | 24 | PW | LI | | 0-0 | 31-31-14 | D05753J | 13 | | | TB0133Z | 80 | BJ | | ALL |
| 284Z | | | LI | | 0-0 | 31-31-14 | D05753J | 15 | | | GDY0012 | S.. | 2 | | ALL |
| 285B | 24 | PW | LJ | | 3-6 | 34-22-19 | TB0133G | 155 | 2 | | D05201P | 20 | | | 050-099 |
| 285B | 24 | PW | LJ | | 5-0 | 34-22-19 | TB0133G | 155 | 2 | | D05201P | 20 | | | 150-156, 162-166 |
| 285B | 24 | PW | LJ | | 5-0 | 34-22-19 | TB0133Z | 155 | BJ | | D05201P | 20 | | | 157, 167-199, 275-299 |
| 285R | 24 | PW | LJ | | 0-0 | 34-22-19 | TB0133G | 154 | 2 | | D05201P | 19 | | | 050-099, 150-156, 162-166 |
| 285R | 24 | PW | LJ | | 0-0 | 34-22-19 | TB0133Z | 154 | BJ | | D05201P | 19 | | | 157, 167-199, 275-299 |
| 285Z | | | LJ | | 0-0 | 34-22-19 | GDY0009 | S.. | 2 | | D05201P | 21 | | | 050-099, 155-157, 167-199, 275-299 |
| 285Z | | | LJ | | 0-0 | 34-22-19 | GDY0008 | S.. | 2 | | D05201P | 21 | | | 150-154 |
| 285Z | | | LJ | | 0-0 | 34-22-19 | GDY0009 | S.. | 2 | * | D05201P | 21 | | | 162-166 |
| 286B | 24 | PW | LK | | 2-6 | 34-61-15 | D04791P | 7 | | | D05733J | 43 | | | 050-099 |
| 286B | 24 | PW | LK | | 6-0 | 34-61-15 | D04791P | 7 | | | D05733J | 43 | | | 150-199, 275-299 |
| 286R | 24 | PW | LK | | 0-0 | 34-61-15 | D04791P | 8 | | | D05733J | 42 | | | ALL |
| 286Z | | | LK | | 0-0 | 34-61-15 | D04791P | 9 | | | D05733J | 44 | | | ALL |
| 287B | 24 | PW | LL | | 3-6 | 34-61-15 | D04791P | 10 | | | TB0133G | 23 | 2 | | 050-099 |
| 287B | 24 | PW | LL | | 5-0 | 34-61-15 | D04791P | 10 | | | TB0133Z | 23 | BJ | | 150-199, 275-299 |
| 287R | 24 | PW | LL | | 0-0 | 34-61-15 | D04791P | 11 | | | TB0133G | 24 | 2 | | 050-099 |
| 287R | 24 | PW | LL | | 0-0 | 34-61-15 | D04791P | 11 | | | TB0133Z | 24 | BJ | | 150-199, 275-299 |
| 287Z | | | LL | | 0-0 | 34-61-15 | D04791P | 17 | | | GDY0003 | S.. | 2 | | 050-099, 162-199, 275-299 |
| 287Z | | | LL | | 0-0 | 34-61-15 | D04791P | 17 | | | GDY0002 | S.. | 2 | | 150-157 |
| 288B | 24 | PW | LM | | 2-10 | 34-61-15 | D04791P | 18 | | | TB0133H | 35 | 2 | | 050-099 |
| 288B | 24 | PW | LM | | 5-0 | 34-61-15 | D04791P | 18 | | | TB0133H | 35 | 2 | | 150-199, 275-299 |
| 288R | 24 | PW | LM | | 0-0 | 34-61-15 | D04791P | 19 | | | TB0133H | 33 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0130
Page 21
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | | | |
| 288Z | | | | LM | 0-0 | 34-61-15 | D04791P | | 20 | | | | | GDY0006 | S.. | 2 | ALL | |
| 290 | 20 | UA | | | 1-6 | 34-55-11 | D00333B | | REF | | LO | | | GDY0001 | S.. | 2 | 050-099 | |
| 290 | 20 | UA | | | 3-0 | 34-55-11 | D00333B | | REF | | LO | | | GDY0001 | S.. | 2 | 150-199, 275-299 | |
| 290B | 24 | PW | LO | | 4-11 | 34-55-11 | D00333B | | E03 | | | | | D04373P | | 29 | 050-099 | |
| 290B | 24 | PW | LO | | 6-0 | 34-55-11 | D00333B | | E03 | | | | | D04373P | | 29 | 150-199, 275-299 | |
| 290R | 24 | PW | LO | | 0-0 | 34-55-11 | D00333B | | D03 | | | | | D04373P | | 16 | ALL | |
| 290Z | | | | | 0-0 | 34-55-11 | D00333B | | REF | | LO | | | D04373P | | 28 | ALL | |
| 291B | 24 | PW | LP | | 3-5 | 34-55-11 | D00333B | | B03 | | | | | TB0133G | | 23 | 050-099 | |
| 291B | 24 | PW | LP | | 4-0 | 34-55-11 | D00333B | | B03 | | | | | TB0133Z | | 23 | BJ | |
| 291R | 24 | PW | LP | | 0-0 | 34-55-11 | D00333B | | A03 | | | | | TB0133G | | 24 | 2 | |
| 291R | 24 | PW | LP | | 0-0 | 34-55-11 | D00333B | | A03 | | | | | TB0133Z | | 24 | BJ | |
| 291Z | | | | LP | 0-0 | 34-55-11 | D00333B | | DED | | | | | GDY0003 | | S.. | 2 | |
| | | | | | | | | | | | | | | | | | | 050-099, 162-199, 275-299 |
| 291Z | | | | LP | 0-0 | 34-55-11 | D00333B | | DED | | | | | GDY0002 | | S.. | 2 | 150-157 |
| 292B | 24 | PW | LQ | | 2-10 | 34-61-12 | D00333B | | H01 | | | | | TB0133G | | 11 | 2 | 050-099 |
| 292B | 24 | PW | LQ | | 4-0 | 34-61-12 | D00333B | | H01 | | | | | TB0133G | | 11 | 2 | 150-199, 275-299 |
| 292R | 24 | PW | LQ | | 0-0 | 34-61-12 | D00333B | | G01 | | | | | TB0133G | | 10 | 2 | ALL |
| 292Z | | | | LQ | 0-0 | 34-61-12 | D00333B | | DED | | | | | GDY0001 | | S.. | 2 | 050-099, 152-199, 275-299 |
| 292Z | | | | LQ | 0-0 | 34-61-12 | D00333B | | DED | | | | | GDY0002 | | S.. | 2 | 150-151 |
| 293B | 24 | PL | LR | | 2-9 | 23-51-12 | D00333B | | B01 | | | | | TB0133F | | C002 | 2 | 050-099 |
| 293B | 24 | PL | LR | | 4-0 | 23-51-12 | D00333B | | B01 | | | | | TB0133F | | C002 | 2 | 150-199, 275-299 |
| 293R | 24 | PL | LR | | 0-0 | 23-51-12 | D00333B | | A01 | | | | | TB0133F | | A002 | 2 | ALL |
| 295B | 24 | PW | LT | | 3-10 | 31-31-14 | D05703J | | 36 | | | | | TB0133Z | | 83 | BJ | 050-099 |
| 295B | 24 | PW | LT | | 5-0 | 31-31-14 | D05703J | | 36 | | | | | TB0133Z | | 83 | BJ | 150-199, 275-299 |
| 295R | 24 | PW | LT | | 0-0 | 31-31-14 | D05703J | | 35 | | | | | TB0133Z | | 82 | BJ | ALL |
| 295Z | | | | LT | 0-0 | 31-31-14 | D05703J | | 37 | | | | | GDY0012 | | S.. | 2 | 050-099, 155-199, 275-299 |
| 295Z | | | | LT | 0-0 | 31-31-14 | D05703J | | 37 | | | | | GDY0013 | | S.. | 2 | 150-154 |
| 298B | 24 | PW | LW | | 2-10 | 34-46-11 | TB0133Y | | C129 | BJ | | | | D05733J | | 33 | | 050-099 |
| 298B | 24 | PW | LW | | 4-0 | 34-46-11 | TB0133Y | | C129 | BJ | | | | D05733J | | 33 | | 150-199, 275-299 |
| 298R | 24 | PW | LW | | 0-0 | 34-46-11 | TB0133Y | | A129 | BJ | | | | D05733J | | 32 | | ALL |
| 298Z | | | | LW | 0-0 | 34-46-11 | GDY0006 | | S.. | 2 | | | | D05733J | | 34 | | ALL |
| 301B | 24 | PM | MA | | 5-0 | 23-51-12 | D04373P | | 25 | | | | | TB0133F | | C001 | 2 | 050-099 |
| 301B | 24 | PM | MA | | 6-0 | 23-51-12 | D04373P | | 25 | | | | | TB0133F | | C001 | 2 | 150-199, 275-299 |
| 301R | 24 | PM | MA | | 0-0 | 23-51-12 | D04373P | | 24 | | | | | TB0133F | | A001 | 2 | ALL |
| 301Y | 24 | PM | MA | | 0-0 | 23-51-12 | D04373P | | 12 | | | | | TB0133F | | A002 | 2 | ALL |
| 302B | 24 | PM | MB | | 3-3 | 23-51-12 | D04735P | | 6 | | | | | TB0133F | | C001 | 2 | 050-099 |
| 302B | 24 | PM | MB | | 4-0 | 23-51-12 | D04735P | | 6 | | | | | TB0133F | | C001 | 2 | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 22

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|-------------------|--------------------|----|----|---------------------------------|-------|----------|-------------|------|------|--------|-----------|------|------|--------|-----------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 302R | 24 | | PM | MB | 0-0 | 23-51-12 | D04735P | | 5 | | TB0133F | A001 | 2 | | ALL |
| 302Y | 24 | | PM | MB | 0-0 | 23-51-12 | D04735P | | 7 | | TB0133F | C002 | 2 | | ALL |
| 303B | 24 | | PM | MC | 2-8 | 34-12-21 | D04151P | | 32 | | D05703J | | 50 | | 050-099 |
| 303B | 24 | | PM | MC | 4-0 | 34-12-21 | D04151P | | 32 | | D05703J | | 50 | | 150-199, 275-299 |
| 303R | 24 | | PM | MC | 0-0 | 34-12-21 | D04151P | | 31 | | D05703J | | 49 | | ALL |
| 303Y | 24 | | PM | MC | 0-0 | 34-12-21 | D04151P | | 33 | | D05703J | | 51 | | ALL |
| 504 | 20 | | UA | | 2-6 | 34-61-15 | D00323B | REF | | UD | GD00012 | S.. | 2 | | 050-099 |
| 504 | 20 | | UA | | 3-0 | 34-61-15 | D00323B | REF | | UD | GD00012 | S.. | 2 | | 150-166, 275-299 |
| 504 | 20 | | UA | | 1-6 | 34-61-15 | D00323B | REF | | UD | GD00013 | S.. | 2 | | 167-199 |
| 504B | 24 | | PW | UD | 4-10 | 34-61-15 | D00323B | REF | ** | | D04735P | | 9 | | 050-099 |
| 504B | 24 | | PW | UD | 6-0 | 34-61-15 | D00323B | REF | ** | | D04735P | | 9 | | 150-166 |
| 504B | 24 | | PW | UD | 6-0 | 34-61-15 | D00323B | B09 | | | D04735P | | 9 | | 167-199, 275-299 |
| 504R | 24 | | PW | UD | 0-0 | 34-61-15 | D00323B | REF | ** | | D04735P | | 8 | | 050-099, 150-166 |
| 504R | 24 | | PW | UD | 0-0 | 34-61-15 | D00323B | A09 | | | D04735P | | 8 | | 167-199, 275-299 |
| 504Z | | | | UD | 0-0 | 34-61-15 | D00323B | REF | | UD | D04735P | | 49 | | ALL |
| 505 | 20 | | UA | | 1-6 | 34-61-15 | D00323B | REF | | UE | GD00013 | S.. | 2 | | 050-099, 167-199 |
| 505 | 20 | | UA | | 3-0 | 34-61-15 | D00323B | REF | | UE | GD00013 | S.. | 2 | | 150-166, 275-299 |
| 505B | 24 | | PW | UE | 4-10 | 34-61-15 | D00323B | REF | ** | | D04735P | | 11 | | 050-099 |
| 505B | 24 | | PW | UE | 6-0 | 34-61-15 | D00323B | REF | ** | | D04735P | | 11 | | 150-199 |
| 505B | 24 | | PW | UE | 6-0 | 34-61-15 | D00323B | H03 | | | D04735P | | 11 | | 275-299 |
| 505R | 24 | | PW | UE | 0-0 | 34-61-15 | D00323B | REF | ** | | D04735P | | 10 | | 050-099, 150-199 |
| 505R | 24 | | PW | UE | 0-0 | 34-61-15 | D00323B | G03 | | | D04735P | | 10 | | 275-299 |
| 505Z | | | | UE | 0-0 | 34-61-15 | D00323B | REF | | UE | D04735P | | 12 | | ALL |
| 506B | 24 | | PW | UF | 2-11 | 31-51-33 | D05733J | | 39 | | D05203P | | 33 | | 050-099 |
| 506B | 24 | | PW | UF | 4-0 | 31-51-33 | D05733J | | 39 | | D05203P | | 33 | | 150-199, 275-299 |
| 506R | 24 | | PW | UF | 0-0 | 31-51-33 | D05733J | | 38 | | D05203P | | 32 | | ALL |
| 506Z | | | | UF | 0-0 | 31-51-33 | D05733J | | 40 | | D05203P | | 34 | | ALL |
| 509B | 24 | | PW | UI | 2-11 | 31-31-20 | D05753J | | 17 | | TB0133G | | 155 | 2 | 050-099 |
| 509B | 24 | | PW | UI | 3-0 | 31-31-20 | D05753J | | 17 | | TB0133G | | 155 | 2 | 150-156, 162-166 |
| 509B | 24 | | PW | UI | 3-0 | 31-31-20 | D05753J | | 17 | | TB0133Z | | 155 | BJ | 157, 167-199, 275-276, 280-299 |
| 509B | 24 | | PW | UI | 4-0 | 31-31-20 | D05753J | | 17 | | TB0133Z | | 155 | BJ | 277-278 |
| 509R | 24 | | PW | UI | 0-0 | 31-31-20 | D05753J | | 16 | | TB0133G | | 154 | 2 | 050-099, 150-156, 162-166 |
| 509R | 24 | | PW | UI | 0-0 | 31-31-20 | D05753J | | 16 | | TB0133Z | | 154 | BJ | 157, 167-199, 275-299 |
| 509Z | | | | UI | 0-0 | 31-31-20 | D05753J | | 18 | | GDY0009 | S.. | 2 | | ALL |
| 519B | 24 | | PW | US | 2-10 | 31-25-11 | D01769A | | D12 | | TB0133G | | 76 | 2 | 050-099 |
| 519B | 24 | | PW | US | 4-0 | 31-25-11 | D01769A | | D12 | | TB0133G | | 76 | 2 | 150-199, 275-299 |
| 519R | 24 | | PW | US | 0-0 | 31-25-11 | D01769A | | C12 | | TB0133G | | 75 | 2 | ALL |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 23
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 519Z | | | | US | 0-0 | 31-25-11 | D01769A | DED | | | GDY0011 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 519Z | | | | US | 0-0 | 31-25-11 | D01769A | DED | | | GDY0012 | S.. | 2 | | 150-154 |
| 526 | 20 | | UA | | 1-6 | 31-35-11 | D01769B | REF | | VA | GDX0010 | S.. | 2 | | ALL |
| 526B | 24 | | PW | VA | 3-1 | 31-35-11 | D01769B | D13 | | | D05753J | 11 | | | 050-099 |
| 526B | 24 | | PW | VA | 4-0 | 31-35-11 | D01769B | D13 | | | D05753J | 11 | | | 150-199, 275-299 |
| 526R | 24 | | PW | VA | 0-0 | 31-35-11 | D01769B | C13 | | | D05753J | 10 | | | ALL |
| 526Z | | | | VA | 0-0 | 31-35-11 | D01769B | REF | | VA | D05753J | 12 | | | ALL |
| 530 | 20 | | UA | | 1-6 | 23-22-12 | D01769A | REF | | VE | GDX0011 | S.. | 2 | | 050-099 |
| 530 | 20 | | UA | | 3-0 | 23-22-12 | D01769A | REF | | VE | GDX0011 | S.. | 2 | | 150-199, 275-299 |
| 530B | 24 | | PW | VE | 3-11 | 23-22-12 | D01769A | F12 | | | D04735P | 54 | | | 050-099 |
| 530B | 24 | | PW | VE | 5-0 | 23-22-12 | D01769A | F12 | | | D04735P | 54 | | | 150-199, 275-299 |
| 530R | 24 | | PW | VE | 0-0 | 23-22-12 | D01769A | E12 | | | D04735P | 50 | | | ALL |
| 530Z | | | | VE | 0-0 | 23-22-12 | D01769A | REF | | VE | D04735P | 48 | | | ALL |
| 538B | 24 | | PW | VM | 2-11 | 31-31-20 | TB0133X | D158 | BJ | | D05753J | 3 | | | 050-099 |
| 538B | 24 | | PW | VM | 4-0 | 31-31-20 | TB0133X | D158 | BJ | | D05753J | 3 | | | 150-154 |
| 538B | 24 | | PW | VM | 5-0 | 31-31-20 | TB0133X | D086 | BJ | | D05753J | 3 | | | 155-199, 275-299 |
| 538R | 24 | | PW | VM | 0-0 | 31-31-20 | TB0133X | C158 | BJ | | D05753J | 2 | | | 050-099, 150-154 |
| 538R | 24 | | PW | VM | 0-0 | 31-31-20 | TB0133X | C086 | BJ | | D05753J | 2 | | | 155-199, 275-299 |
| 538Z | | | | VM | 0-0 | 31-31-20 | D05753J | 1 | | | GDY0009 | S.. | 2 | | 050-099, 150-154 |
| 538Z | | | | VM | 0-0 | 31-31-20 | D05753J | 1 | | | GDY0013 | S.. | 2 | | 155-199, 275-299 |
| 540B | 24 | | PW | VO | 3-4 | 31-35-11 | D04429P | 12 | | | TB0133Y | C164 | BJ | | 050-099 |
| 540B | 24 | | PW | VO | 4-0 | 31-35-11 | D04429P | 12 | | | TB0133Y | C164 | BJ | | 150-199, 275-299 |
| 540R | 24 | | PW | VO | 0-0 | 31-35-11 | D04429P | 11 | | | TB0133Y | A164 | BJ | | ALL |
| 540Z | | | | VO | 0-0 | 31-35-11 | D04429P | 13 | | | GDY0010 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 540Z | | | | VO | 0-0 | 31-35-11 | D04429P | 13 | | | GDY0011 | S.. | 2 | | 150-154 |
| 541B | 24 | | PW | VP | 2-8 | 31-35-11 | D01769A | H09 | | | TB0133Y | C164 | BJ | | 050-099 |
| 541B | 24 | | PW | VP | 4-0 | 31-35-11 | D01769A | H09 | | | TB0133Y | C164 | BJ | | 150-199, 275-299 |
| 541R | 24 | | PW | VP | 0-0 | 31-35-11 | D01769A | G09 | | | TB0133Y | A164 | BJ | | ALL |
| 541Z | | | | VP | 0-0 | 31-35-11 | D01769A | DED | | | GDY0010 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 541Z | | | | VP | 0-0 | 31-35-11 | D01769A | DED | | | GDY0011 | S.. | 2 | | 150-154 |
| 542B | 24 | | PW | VQ | 3-2 | 31-35-12 | D01769A | H08 | | | TB0133X | D086 | BJ | | 050-099 |
| 542B | 24 | | PW | VQ | 4-0 | 31-35-12 | D01769A | H08 | | | TB0133X | D158 | BJ | | 150-154 |
| 542B | 24 | | PW | VQ | 4-0 | 31-35-12 | D01769A | H08 | | | TB0133X | D086 | BJ | | 155-199, 275-299 |
| 542R | 24 | | PW | VQ | 0-0 | 31-35-12 | D01769A | G08 | | | TB0133X | C086 | BJ | | 050-099, 155-199, 275-299 |
| 542R | 24 | | PW | VQ | 0-0 | 31-35-12 | D01769A | G08 | | | TB0133X | C158 | BJ | | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 24

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|-----|---------------------------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0133 | 286T0133 | | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 542Z | | | | VQ | 0-0 | 31-35-12 | D01769A | DED | | | GDY0013 | S.. | 2 | | 050-099, 155-199, 275-299 | |
| 542Z | | | | VQ | 0-0 | 31-35-12 | D01769A | DED | | | GDY0010 | S.. | 2 | | 150-154 | |
| 543B | 24 | PW | | VR | 3-0 | 31-35-12 | D01769A | D14 | | | TB0133Z | 81 | BJ | | 050-099 | |
| 543B | 24 | PW | | VR | 4-0 | 31-35-12 | D01769A | D14 | | | TB0133Z | 81 | BJ | | 150-199, 275-299 | |
| 543R | 24 | PW | | VR | 0-0 | 31-35-12 | D01769A | C14 | | | TB0133Z | 80 | BJ | | ALL | |
| 543Z | | | | VR | 0-0 | 31-35-12 | D01769A | DED | | | GDY0012 | S.. | 2 | | ALL | |
| 544B | 24 | PW | | VS | 3-0 | 31-35-12 | D01769A | H14 | | | TB0133Z | 83 | BJ | | 050-099 | |
| 544B | 24 | PW | | VS | 4-0 | 31-35-12 | D01769A | H14 | | | TB0133Z | 83 | BJ | | 150-199, 275-299 | |
| 544R | 24 | PW | | VS | 0-0 | 31-35-12 | D01769A | G14 | | | TB0133Z | 82 | BJ | | ALL | |
| 544Z | | | | VS | 0-0 | 31-35-12 | D01769A | DED | | | GDY0013 | S.. | 2 | | ALL | |
| 546B | 24 | PW | | VU | 2-9 | 31-35-12 | D01769B | B12 | | | TB0133G | 155 | 2 | | 050-099 | |
| 546B | 24 | PW | | VU | 4-0 | 31-35-12 | D01769B | B12 | | | TB0133G | 155 | 2 | | 150-156, 162-166 | |
| 546B | 24 | PW | | VU | 4-0 | 31-35-12 | D01769B | B12 | | | TB0133Z | 155 | BJ | | 157, 167-199, 275-299 | |
| 546R | 24 | PW | | VU | 0-0 | 31-35-12 | D01769B | A12 | | | TB0133Z | 154 | BJ | | 050-099, 150-156, 162-166 | |
| 546Z | | | | VU | 0-0 | 31-35-12 | D01769B | DED | | | GDY0009 | S.. | 2 | | 157, 167-199, 275-299 | |
| 546Z | | | | VU | 0-0 | 31-35-12 | D01769B | DED | | | GDY0009 | S.. | 2 | * | 162-166 | |
| 547B | 24 | PW | | VV | 2-11 | 31-35-12 | D01769B | H13 | | | TB0133H | 59 | 2 | | 050-099 | |
| 547B | 24 | PW | | VV | 4-0 | 31-35-12 | D01769B | H13 | | | TB0133H | 59 | 2 | | 150-199, 275-299 | |
| 547R | 24 | PW | | VV | 0-0 | 31-35-12 | D01769B | G13 | | | TB0133H | 57 | 2 | | ALL | |
| 547Z | | | | VV | 0-0 | 31-35-12 | D01769B | DED | | | GDY0009 | S.. | 2 | | ALL | |
| 548B | 24 | PW | | VW | 3-2 | 31-35-12 | D01769A | B15 | | | TB0133X | B086 | BJ | | 050-099 | |
| 548B | 24 | PW | | VW | 4-0 | 31-35-12 | D01769A | B15 | | | TB0133X | D160 | BJ | | 150-154 | |
| 548B | 24 | PW | | VW | 4-0 | 31-35-12 | D01769A | B15 | | | TB0133X | B086 | BJ | | 155-199, 275-299 | |
| 548R | 24 | PW | | VW | 0-0 | 31-35-12 | D01769A | A15 | | | TB0133X | A086 | BJ | | 050-099, 155-199, 275-299 | |
| 548R | 24 | PW | | VW | 0-0 | 31-35-12 | D01769A | A15 | | | TB0133X | C160 | BJ | | 150-154 | |
| 548Z | | | | VW | 0-0 | 31-35-12 | D01769A | DED | | | GDY0013 | S.. | 2 | | 050-099, 155-199, 275-299 | |
| 548Z | | | | VW | 0-0 | 31-35-12 | D01769A | DED | | | GDY0010 | S.. | 2 | | 150-154 | |
| 549B | 24 | PW | | VX | 3-4 | 31-35-12 | D01769A | D10 | | | TB0133X | B038 | BJ | | 050-099 | |
| 549B | 24 | PW | | VX | 5-0 | 31-35-12 | D01769A | D10 | | | TB0133X | B038 | BJ | | 150-199, 275-299 | |
| 549R | 24 | PW | | VX | 0-0 | 31-35-12 | D01769A | C10 | | | TB0133X | A038 | BJ | | ALL | |
| 549Z | | | | VX | 0-0 | 31-35-12 | D01769A | DED | | | GDY0007 | S.. | 2 | | ALL | |
| 550B | 24 | PW | | VY | 3-4 | 31-35-12 | D01769A | F14 | | | TB0133X | D038 | BJ | | 050-099 | |
| 550B | 24 | PW | | VY | 5-0 | 31-35-12 | D01769A | F14 | | | TB0133X | D038 | BJ | | 150-199, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 25
Jan 21/2005



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|----|---------------------------------|----------|----------|---------|----|-----|-------|---------|-------|------|------|---------------------------|-------|------|
| | | | | | Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | | |
| 550R | 24 | PW | VY | | 0-0 | 31-35-12 | D01769A | | E14 | | TB0133X | C038 | BJ | | ALL | | |
| 550Z | | | VY | | 0-0 | 31-35-12 | D01769A | | DED | | GDY0007 | S.. | 2 | | ALL | | |
| 551B | 24 | PW | WA | | 3-4 | 31-35-12 | D01769B | | K10 | | TB0133X | B039 | BJ | | 050-099 | | |
| 551B | 24 | PW | WA | | 5-0 | 31-35-12 | D01769B | | K10 | | TB0133X | B039 | BJ | | 150-199, 275-299 | | |
| 551R | 24 | PW | WA | | 0-0 | 31-35-12 | D01769B | | J10 | | TB0133X | A039 | BJ | | ALL | | |
| 551Z | | | WA | | 0-0 | 31-35-12 | D01769B | | DED | | GDY0007 | S.. | 2 | | ALL | | |
| 552B | 24 | PW | WB | | 3-4 | 31-35-12 | D01769B | | F14 | | TB0133X | D039 | BJ | | 050-099 | | |
| 552B | 24 | PW | WB | | 5-0 | 31-35-12 | D01769B | | F14 | | TB0133X | D039 | BJ | | 150-199, 275-299 | | |
| 552R | 24 | PW | WB | | 0-0 | 31-35-12 | D01769B | | E14 | | TB0133X | C039 | BJ | | ALL | | |
| 552Z | | | WB | | 0-0 | 31-35-12 | D01769B | | DED | | GDY0007 | S.. | 2 | | ALL | | |
| 553B | 24 | PW | WC | | 3-1 | 31-35-12 | D01769B | | K12 | | TB0133X | B141 | BJ | | 050-099 | | |
| 553B | 24 | PW | WC | | 4-0 | 31-35-12 | D01769B | | K12 | | TB0133X | B157 | BJ | | 150-154 | | |
| 553B | 24 | PW | WC | | 4-0 | 31-35-12 | D01769B | | K12 | | TB0133X | B141 | BJ | | 155-199, 275-299 | | |
| 553R | 24 | PW | WC | | 0-0 | 31-35-12 | D01769B | | J12 | | TB0133X | A141 | BJ | | 050-099, 155-199, 275-299 | | |
| 553R | 24 | PW | WC | | 0-0 | 31-35-12 | D01769B | | J12 | | TB0133X | A157 | BJ | | 150-154 | | |
| 553Z | | | WC | | 0-0 | 31-35-12 | D01769B | | DED | | GDY0007 | S.. | 2 | | 050-099, 155-199, 275-299 | | |
| 553Z | | | WC | | 0-0 | 31-35-12 | D01769B | | DED | | GDY0009 | S.. | 2 | | 150-154 | | |
| 554B | 24 | PW | WD | | 3-1 | 31-35-12 | D01769B | | F12 | | TB0133X | D141 | BJ | | 050-099 | | |
| 554B | 24 | PW | WD | | 4-0 | 31-35-12 | D01769B | | F12 | | TB0133X | D157 | BJ | | 150-154 | | |
| 554B | 24 | PW | WD | | 4-0 | 31-35-12 | D01769B | | F12 | | TB0133X | D141 | BJ | | 155-199, 275-299 | | |
| 554R | 24 | PW | WD | | 0-0 | 31-35-12 | D01769B | | E12 | | TB0133X | C141 | BJ | | 050-099, 155-199, 275-299 | | |
| 554R | 24 | PW | WD | | 0-0 | 31-35-12 | D01769B | | E12 | | TB0133X | C157 | BJ | | 150-154 | | |
| 554Z | | | WD | | 0-0 | 31-35-12 | D01769B | | DED | | GDY0007 | S.. | 2 | | 050-099, 155-199, 275-299 | | |
| 554Z | | | WD | | 0-0 | 31-35-12 | D01769B | | DED | | GDY0009 | S.. | 2 | | 150-154 | | |
| 555B | 24 | PW | WE | | 3-1 | 31-35-12 | D01769B | | D10 | | TB0133X | B142 | BJ | | 050-099 | | |
| 555B | 24 | PW | WE | | 4-0 | 31-35-12 | D01769B | | D10 | | TB0133X | B158 | BJ | | 150-154 | | |
| 555B | 24 | PW | WE | | 4-0 | 31-35-12 | D01769B | | D10 | | TB0133X | B142 | BJ | | 155-199, 275-299 | | |
| 555R | 24 | PW | WE | | 0-0 | 31-35-12 | D01769B | | C10 | | TB0133X | A142 | BJ | | 050-099, 155-199, 275-299 | | |
| 555R | 24 | PW | WE | | 0-0 | 31-35-12 | D01769B | | C10 | | TB0133X | A158 | BJ | | 150-154 | | |
| 555Z | | | WE | | 0-0 | 31-35-12 | D01769B | | DED | | GDY0007 | S.. | 2 | | 050-099, 155-199, 275-299 | | |
| 555Z | | | WE | | 0-0 | 31-35-12 | D01769B | | DED | | GDY0009 | S.. | 2 | | 150-154 | | |
| 556 | 20 | UA | | | 1-6 | 31-35-11 | D01769A | | | WF | GDY0012 | S.. | 2 | | 050-099 | | |
| 556 | 20 | UA | | | 1-6 | 31-35-11 | D01769A | | | WF | GDY0010 | S.. | 2 | | 150-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 26

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 556B | 24 | | PW | WF | 3-11 | 31-35-11 | D01769A | K09 | | | D04735P | 43 | | | 050-099 |
| 556B | 24 | | PW | WF | 6-0 | 31-35-11 | D01769A | K09 | | | D04735P | 43 | | | 150-199, 275-299 |
| 556R | 24 | | PW | WF | 0-0 | 31-35-11 | D01769A | J09 | | | D04735P | 42 | | | ALL |
| 556Z | | | | WF | 0-0 | 31-35-11 | D01769A | | | WF | D04735P | 44 | | | ALL |
| 559B | 24 | | PW | WI | 2-11 | 31-35-11 | TB0133Z | 62 | BJ | | D01769A | H11 | | | 050-099 |
| 559B | 24 | | PW | WI | 4-0 | 31-35-11 | TB0133Z | 62 | BJ | | D01769A | H11 | | | 150-199, 275-299 |
| 559R | 24 | | PW | WI | 0-0 | 31-35-11 | TB0133Z | 61 | BJ | | D01769A | G11 | | | ALL |
| 559Z | | | | WI | 0-0 | 31-35-11 | D01769A | DED | | | GDY0010 | S.. | 2 | | 050-099 |
| 559Z | | | | WI | 0-0 | 31-35-11 | GDY0010 | S.. | 2 | | D01769A | DED | | | 150-199, 275-299 |
| 561B | 24 | | PW | WK | 3-2 | 31-35-12 | D01769A | H10 | | | TB0133X | B085 | BJ | | 050-099 |
| 561B | 24 | | PW | WK | 4-0 | 31-35-12 | D01769A | H10 | | | TB0133X | D159 | BJ | | 150-154 |
| 561B | 24 | | PW | WK | 4-0 | 31-35-12 | D01769A | H10 | | | TB0133X | B085 | BJ | | 155-199, 275-299 |
| 561R | 24 | | PW | WK | 0-0 | 31-35-12 | D01769A | G10 | | | TB0133X | A085 | BJ | | 050-099, 155-199, 275-299 |
| 561R | 24 | | PW | WK | 0-0 | 31-35-12 | D01769A | G10 | | | TB0133X | C159 | BJ | | 150-154 |
| 561Z | | | | WK | 0-0 | 31-35-12 | D01769A | DED | | | GDY0013 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 561Z | | | | WK | 0-0 | 31-35-12 | D01769A | DED | | | GDY0010 | S.. | 2 | | 150-154 |
| 562B | 24 | | PW | WL | 3-2 | 31-35-12 | D01769A | F08 | | | TB0133X | D085 | BJ | | 050-099 |
| 562B | 24 | | PW | WL | 4-0 | 31-35-12 | D01769A | F08 | | | TB0133X | B160 | BJ | | 150-154 |
| 562B | 24 | | PW | WL | 4-0 | 31-35-12 | D01769A | F08 | | | TB0133X | D085 | BJ | | 155-199, 275-299 |
| 562R | 24 | | PW | WL | 0-0 | 31-35-12 | D01769A | E08 | | | TB0133X | C085 | BJ | | 050-099, 155-199, 275-299 |
| 562R | 24 | | PW | WL | 0-0 | 31-35-12 | D01769A | E08 | | | TB0133X | A160 | BJ | | 150-154 |
| 562Z | | | | WL | 0-0 | 31-35-12 | D01769A | DED | | | GDY0013 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 562Z | | | | WL | 0-0 | 31-35-12 | D01769A | DED | | | GDY0010 | S.. | 2 | | 150-154 |
| 563 | 20 | | UA | | 1-6 | 31-35-12 | D01769A | REF | | WM | GDX0013 | S.. | 2 | | 050-099 |
| 563 | 20 | | UA | | 1-6 | 31-35-12 | D01769A | REF | | WM | GDX0010 | S.. | 2 | | 150-199, 275-299 |
| 563B | 24 | | PW | WM | 4-0 | 31-35-12 | D01769A | B08 | | | D04229P | 2 | | | 050-099 |
| 563B | 24 | | PW | WM | 5-0 | 31-35-12 | D01769A | B08 | | | D04229P | 2 | | | 150-199, 275-299 |
| 563R | 24 | | PW | WM | 0-0 | 31-35-12 | D01769A | A08 | | | D04229P | 1 | | | ALL |
| 563Z | | | | WM | 0-0 | 31-35-12 | D01769A | REF | | WM | D04229P | 3 | | | ALL |
| 564 | 20 | | UA | | 1-6 | 31-35-12 | D01769B | REF | | WN | GDX0010 | S.. | 2 | | ALL |
| 564B | 24 | | PW | WN | 4-0 | 31-35-12 | D01769B | H12 | | | D04229P | 5 | | | 050-099 |
| 564B | 24 | | PW | WN | 5-0 | 31-35-12 | D01769B | H12 | | | D04229P | 5 | | | 150-199, 275-299 |
| 564R | 24 | | PW | WN | 0-0 | 31-35-12 | D01769B | G12 | | | D04229P | 4 | | | ALL |
| 564Z | | | | WN | 0-0 | 31-35-12 | D01769B | REF | | WN | D04229P | 6 | | | ALL |
| 565 | 20 | | UA | | 1-6 | 31-35-12 | D01769A | REF | | WO | GDX0010 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 27

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | |
| 565B | 24 | PW | W0 | | 4-0 | 31-35-12 | D01769A | | B13 | | | D04229P | 8 | | | 050-099 |
| 565B | 24 | PW | W0 | | 5-0 | 31-35-12 | D01769A | | B13 | | | D04229P | 8 | | | 150-199, 275-299 |
| 565R | 24 | PW | W0 | | 0-0 | 31-35-12 | D01769A | | A13 | | | D04229P | 7 | | | ALL |
| 565Z | | | W0 | | 0-0 | 31-35-12 | D01769A | | REF | WO | | D04229P | 9 | | | ALL |
| 566 | 20 | UA | | | 1-6 | 31-35-12 | D01769A | | REF | WP | | GDX0010 | S.. | 2 | | ALL |
| 566B | 24 | PW | WP | | 3-1 | 31-35-12 | D01769A | | K10 | | | D05753J | 29 | | | 050-099 |
| 566B | 24 | PW | WP | | 4-0 | 31-35-12 | D01769A | | K10 | | | D05753J | 29 | | | 150-199, 275-299 |
| 566R | 24 | PW | WP | | 0-0 | 31-35-12 | D01769A | | J10 | | | D05753J | 28 | | | ALL |
| 566Z | | | WP | | 0-0 | 31-35-12 | D01769A | | REF | WP | | D05753J | 30 | | | ALL |
| 567 | 20 | UA | | | 1-6 | 31-35-12 | D01769A | | REF | WQ | | GDX0010 | S.. | 2 | | ALL |
| 567B | 24 | PW | WQ | | 3-1 | 31-35-12 | D01769A | | K13 | | | D05753J | 32 | | | 050-099 |
| 567B | 24 | PW | WQ | | 4-0 | 31-35-12 | D01769A | | K13 | | | D05753J | 32 | | | 150-199, 275-299 |
| 567R | 24 | PW | WQ | | 0-0 | 31-35-12 | D01769A | | J13 | | | D05753J | 31 | | | ALL |
| 567Z | | | WQ | | 0-0 | 31-35-12 | D01769A | | REF | WQ | | D05753J | 33 | | | ALL |
| 568 | 20 | UA | | | 1-6 | 31-35-12 | D01769A | | REF | WR | | GDX0010 | S.. | 2 | | ALL |
| 568B | 24 | PW | WR | | 3-1 | 31-35-12 | D01769A | | K12 | | | D05753J | 35 | | | 050-099 |
| 568B | 24 | PW | WR | | 4-0 | 31-35-12 | D01769A | | K12 | | | D05753J | 35 | | | 150-199, 275-299 |
| 568R | 24 | PW | WR | | 0-0 | 31-35-12 | D01769A | | J12 | | | D05753J | 34 | | | ALL |
| 568Z | | | WR | | 0-0 | 31-35-12 | D01769A | | REF | WR | | D05753J | 36 | | | ALL |
| 570 | 20 | UA | | | 1-6 | 31-35-12 | D01769A | | REF | WT | | GDX0011 | S.. | 2 | | ALL |
| 570B | 24 | PW | WT | | 3-1 | 31-35-12 | D01769A | | F13 | | | D05753J | 39 | | | 050-099 |
| 570B | 24 | PW | WT | | 4-0 | 31-35-12 | D01769A | | F13 | | | D05753J | 39 | | | 150-199, 275-299 |
| 570R | 24 | PW | WT | | 0-0 | 31-35-12 | D01769A | | E13 | | | D05753J | 38 | | | ALL |
| 570Z | | | WT | | 0-0 | 31-35-12 | D01769A | | REF | WT | | D05753J | 40 | | | ALL |
| 571 | 20 | UA | | | 1-6 | 31-35-12 | D01769A | | REF | WU | | GDX0011 | S.. | 2 | | ALL |
| 571B | 24 | PW | WU | | 3-1 | 31-35-12 | D01769A | | B12 | | | D05753J | 42 | | | 050-099 |
| 571B | 24 | PW | WU | | 4-0 | 31-35-12 | D01769A | | B12 | | | D05753J | 42 | | | 150-199, 275-299 |
| 571R | 24 | PW | WU | | 0-0 | 31-35-12 | D01769A | | A12 | | | D05753J | 41 | | | ALL |
| 571Z | | | WU | | 0-0 | 31-35-12 | D01769A | | REF | WU | | D05753J | 43 | | | ALL |
| 572 | 20 | UA | | | 1-6 | 31-35-12 | D01769B | | REF | WV | | GDX0011 | S.. | 2 | | ALL |
| 572B | 24 | PW | WV | | 3-1 | 31-35-12 | D01769B | | B08 | | | D05753J | 47 | | | 050-099 |
| 572B | 24 | PW | WV | | 4-0 | 31-35-12 | D01769B | | B08 | | | D05753J | 47 | | | 150-199, 275-299 |
| 572R | 24 | PW | WV | | 0-0 | 31-35-12 | D01769B | | A08 | | | D05753J | 46 | | | ALL |
| 572Z | | | WV | | 0-0 | 31-35-12 | D01769B | | REF | WV | | D05753J | 48 | | | ALL |
| 573 | 20 | UA | | | 1-6 | 31-35-12 | D01769A | | REF | WW | | GDX0011 | S.. | 2 | | ALL |
| 573B | 24 | PW | WW | | 3-1 | 31-35-12 | D01769A | | B14 | | | D05753J | 26 | | | 050-099 |
| 573B | 24 | PW | WW | | 4-0 | 31-35-12 | D01769A | | B14 | | | D05753J | 26 | | | 150-199, 275-299 |
| 573R | 24 | PW | WW | | 0-0 | 31-35-12 | D01769A | | A14 | | | D05753J | 25 | | | ALL |
| 573Z | | | WW | | 0-0 | 31-35-12 | D01769A | | REF | WW | | D05753J | 27 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 28

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|---------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 574 | 20 | | UA | | 1-6 | 31-35-12 | D01769B | | REF | | WX | GDX0011 | S.. | 2 | ALL |
| 574B | 24 | | PW | WX | 3-1 | 31-35-12 | D01769B | | B13 | | | D05753J | 8 | | 050-099 |
| 574B | 24 | | PW | WX | 4-0 | 31-35-12 | D01769B | | B13 | | | D05753J | 8 | | 150-199, 275-299 |
| 574R | 24 | | PW | WX | 0-0 | 31-35-12 | D01769B | | A13 | | | D05753J | 7 | | ALL |
| 574Z | | | | WX | 0-0 | 31-35-12 | D01769B | | REF | | WX | D05753J | 9 | | ALL |
| 575B | 24 | | PW | WY | 3-0 | 31-35-13 | D01769B | | F13 | | | TB0133X | B049 | BJ | 050-099 |
| 575B | 24 | | PW | WY | 4-0 | 31-35-13 | D01769B | | F13 | | | TB0133X | B049 | BJ | 150-199, 275-299 |
| 575R | 24 | | PW | WY | 0-0 | 31-35-13 | D01769B | | E13 | | | TB0133X | A049 | BJ | ALL |
| 575Z | | | | WY | 0-0 | 31-35-13 | D01769B | | DED | | | GDY0008 | S.. | 2 | 050-099, 155-199, 275-299 |
| 575Z | | | | WY | 0-0 | 31-35-13 | D01769B | | DED | | | GDY0007 | S.. | 2 | 150-154 |
| 576B | 24 | | PW | XA | 3-0 | 31-35-13 | D01769B | | D14 | | | TB0133X | D049 | BJ | 050-099 |
| 576B | 24 | | PW | XA | 4-0 | 31-35-13 | D01769B | | D14 | | | TB0133X | D049 | BJ | 150-199, 275-299 |
| 576R | 24 | | PW | XA | 0-0 | 31-35-13 | D01769B | | C14 | | | TB0133X | C049 | BJ | ALL |
| 576Z | | | | XA | 0-0 | 31-35-13 | D01769B | | DED | | | GDY0008 | S.. | 2 | 050-099, 155-199, 275-299 |
| 576Z | | | | XA | 0-0 | 31-35-13 | D01769B | | DED | | | GDY0007 | S.. | 2 | 150-154 |
| 577B | 24 | | PW | XB | 3-0 | 31-35-13 | D01769B | | K14 | | | TB0133X | B050 | BJ | 050-099 |
| 577B | 24 | | PW | XB | 4-0 | 31-35-13 | D01769B | | K14 | | | TB0133X | B050 | BJ | 150-199, 275-299 |
| 577R | 24 | | PW | XB | 0-0 | 31-35-13 | D01769B | | J14 | | | TB0133X | A050 | BJ | ALL |
| 577Z | | | | XB | 0-0 | 31-35-13 | D01769B | | DED | | | GDY0008 | S.. | 2 | ALL |
| 578B | 24 | | PW | XC | 3-0 | 31-35-13 | D01769B | | H14 | | | TB0133X | D050 | BJ | 050-099 |
| 578B | 24 | | PW | XC | 4-0 | 31-35-13 | D01769B | | H14 | | | TB0133X | D050 | BJ | 150-199, 275-299 |
| 578R | 24 | | PW | XC | 0-0 | 31-35-13 | D01769B | | G14 | | | TB0133X | C050 | BJ | ALL |
| 578Z | | | | XC | 0-0 | 31-35-13 | D01769B | | DED | | | GDY0008 | S.. | 2 | ALL |
| 579B | 24 | | PW | XD | 3-0 | 31-35-13 | D01769B | | D08 | | | TB0133X | D051 | BJ | 050-099 |
| 579B | 24 | | PW | XD | 4-0 | 31-35-13 | D01769B | | D08 | | | TB0133X | D051 | BJ | 150-199, 275-299 |
| 579R | 24 | | PW | XD | 0-0 | 31-35-13 | D01769B | | C08 | | | TB0133X | C051 | BJ | ALL |
| 579Z | | | | XD | 0-0 | 31-35-13 | D01769B | | DED | | | GDY0008 | S.. | 2 | ALL |
| 580B | 24 | | PW | XE | 3-0 | 31-35-13 | D01769B | | H08 | | | TB0133X | B052 | BJ | 050-099 |
| 580B | 24 | | PW | XE | 4-0 | 31-35-13 | D01769B | | H08 | | | TB0133X | B052 | BJ | 150-199, 275-299 |
| 580R | 24 | | PW | XE | 0-0 | 31-35-13 | D01769B | | G08 | | | TB0133X | A052 | BJ | ALL |
| 580Z | | | | XE | 0-0 | 31-35-13 | D01769B | | DED | | | GDY0009 | S.. | 2 | 050-099, 155-199, 275-299 |
| 580Z | | | | XE | 0-0 | 31-35-13 | D01769B | | DED | | | GDY0008 | S.. | 2 | 150-154 |
| 581 | 20 | | UA | | 1-6 | 31-35-13 | D01769A | | REF | | XF | GDX0010 | S.. | 2 | ALL |
| 581B | 24 | | PW | XF | 3-11 | 31-35-13 | D01769A | | K08 | | | D04735P | 46 | | 050-099 |
| 581B | 24 | | PW | XF | 5-0 | 31-35-13 | D01769A | | K08 | | | D04735P | 46 | | 150-199, 275-299 |
| 581R | 24 | | PW | XF | 0-0 | 31-35-13 | D01769A | | J08 | | | D04735P | 45 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 29

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | |
| 581Z | | | | XF | 0-0 | 31-35-13 | D01769A | | REF | | XF | D04735P | 47 | | | ALL |
| 582B | 24 | PW | | XG | 3-0 | 31-35-13 | D01769A | | H12 | | | TB0133X | D052 | BJ | | 050-099 |
| 582B | 24 | PW | | XG | 4-0 | 31-35-13 | D01769A | | H12 | | | TB0133X | D052 | BJ | | 150-199, 275-299 |
| 582R | 24 | PW | | XG | 0-0 | 31-35-13 | D01769A | | G12 | | | TB0133X | C052 | BJ | | ALL |
| 582Z | | | | XG | 0-0 | 31-35-13 | D01769A | | DED | | | GDY0009 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 582Z | | | | XG | 0-0 | 31-35-13 | D01769A | | DED | | | GDY0008 | S.. | 2 | | 150-154 |
| 583B | 24 | PW | | XH | 3-1 | 31-35-13 | D01769A | | K14 | | | TB0133H | 190 | 2 | | 050-099 |
| 583B | 24 | PW | | XH | 4-0 | 31-35-13 | D01769A | | K14 | | | TB0133H | 190 | 2 | | 150-199, 275-299 |
| 583R | 24 | PW | | XH | 0-0 | 31-35-13 | D01769A | | J14 | | | TB0133H | 188 | 2 | | ALL |
| 583Z | | | | XH | 0-0 | 31-35-13 | D01769A | | DED | | | GDY0013 | S.. | 2 | | ALL |
| 584B | 24 | PW | | XI | 2-8 | 31-35-13 | D01769A | | B10 | | | TB0133G | 162 | 2 | | 050-099 |
| 584B | 24 | PW | | XI | 4-0 | 31-35-13 | D01769A | | B10 | | | TB0133G | 162 | 2 | | 150-199, 275-299 |
| 584R | 24 | PW | | XI | 0-0 | 31-35-13 | D01769A | | A10 | | | TB0133G | 161 | 2 | | ALL |
| 584Z | | | | XI | 0-0 | 31-35-13 | D01769A | | DED | | | GDY0010 | S.. | 2 | | ALL |
| 585B | 24 | PW | | XJ | 2-9 | 31-35-13 | D01769A | | D08 | | | TB0133G | 153 | 2 | | 050-099 |
| 585B | 24 | PW | | XJ | 4-0 | 31-35-13 | D01769A | | D08 | | | TB0133G | 153 | 2 | | 150-199, 275-299 |
| 585R | 24 | PW | | XJ | 0-0 | 31-35-13 | D01769A | | C08 | | | TB0133G | 152 | 2 | | ALL |
| 585Z | | | | XJ | 0-0 | 31-35-13 | D01769A | | DED | | | GDY0009 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 585Z | | | | XJ | 0-0 | 31-35-13 | D01769A | | DED | | | GDY0008 | S.. | 2 | | 150-154 |
| 586 | 20 | UA | | | 1-6 | 31-35-16 | D01735A | | REF | | XK | GDX0008 | S.. | 2 | | ALL |
| 586B | 24 | PW | | XK | 2-11 | 31-35-16 | D01769A | | D09 | | | D01735A | A02 | | | 050-099 |
| 586B | 24 | PW | | XK | 4-0 | 31-35-16 | D01769A | | D09 | | | D01735A | A02 | | | 150-199, 275-299 |
| 586R | 24 | PW | | XK | 0-0 | 31-35-16 | D01769A | | C09 | | | D01735A | A01 | | | ALL |
| 586Z | | | | XK | 0-0 | 31-35-16 | D01769A | | DED | | | D01735A | REF | | XK | ALL |
| 587 | 20 | UA | | | 1-6 | 31-35-16 | D01735A | | REF | | XL | GDX0008 | S.. | 2 | | ALL |
| 587B | 24 | PW | | XL | 2-11 | 31-35-16 | D01769B | | B04 | | | D01735A | K02 | | | 050-099 |
| 587B | 24 | PW | | XL | 4-0 | 31-35-16 | D01769B | | B04 | | | D01735A | K02 | | | 150-199, 275-299 |
| 587R | 24 | PW | | XL | 0-0 | 31-35-16 | D01769B | | A04 | | | D01735A | K01 | | | ALL |
| 587Z | | | | XL | 0-0 | 31-35-16 | D01769B | | DED | | | D01735A | REF | | XL | ALL |
| 588 | 20 | UA | | | 1-6 | 31-35-16 | D01735A | | REF | | XM | GDX0008 | S.. | 2 | | ALL |
| 588B | 24 | PW | | XM | 2-11 | 31-35-16 | D01769B | | D04 | | | D01735A | D02 | | | 050-099 |
| 588B | 24 | PW | | XM | 4-0 | 31-35-16 | D01769B | | D04 | | | D01735A | D02 | | | 150-199, 275-299 |
| 588R | 24 | PW | | XM | 0-0 | 31-35-16 | D01769B | | C04 | | | D01735A | D01 | | | ALL |
| 588Z | | | | XM | 0-0 | 31-35-16 | D01769B | | DED | | | D01735A | REF | | XM | ALL |
| 589 | 20 | UA | | | 1-6 | 31-35-16 | D01735A | | REF | | XN | GDX0008 | S.. | 2 | | ALL |
| 589B | 24 | PW | | XN | 2-11 | 31-35-16 | D01769B | | F04 | | | D01735A | G02 | | | 050-099 |
| 589B | 24 | PW | | XN | 4-0 | 31-35-16 | D01769B | | F04 | | | D01735A | G02 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 30

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 589R | 24 | PW | XN | | 0-0 | 31-35-16 | D01769B | E04 | | | D01735A | G01 | | | ALL |
| 589Z | | | XN | | 0-0 | 31-35-16 | D01769B | DED | | | D01735A | REF | | XN | ALL |
| 590B | 24 | PW | XO | | 4-0 | 31-36-11 | D05753J | 52 | | | TB0133Z | 48 | BJ | | ALL |
| 590R | 24 | PW | XO | | 0-0 | 31-36-11 | D05753J | 51 | | | TB0133Z | 47 | BJ | | ALL |
| 590Z | | | XO | | 0-0 | 31-36-11 | D05753J | 50 | | | GDY0008 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 590Z | | | XO | | 0-0 | 31-36-11 | D05753J | 50 | | | GDY0007 | S.. | 2 | | 150-154 |
| 592B | 24 | PW | XQ | | 3-9 | 31-36-11 | D04735P | 36 | | | TB0133Z | 48 | BJ | | 050-099 |
| 592B | 24 | PW | XQ | | 5-0 | 31-36-11 | D04735P | 36 | | | TB0133Z | 48 | BJ | | 150-199, 275-299 |
| 592R | 24 | PW | XQ | | 0-0 | 31-36-11 | D04735P | 35 | | | TB0133Z | 47 | BJ | | ALL |
| 592Z | | | XQ | | 0-0 | 31-36-11 | D04735P | 37 | | | GDY0008 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 592Z | | | XQ | | 0-0 | 31-36-11 | D04735P | 37 | | | GDY0007 | S.. | 2 | | 150-154 |
| 593B | 24 | PW | XR | | 3-11 | 31-36-11 | D00323B | H05 | | | TB0133Z | 48 | BJ | | 050-099 |
| 593B | 24 | PW | XR | | 5-0 | 31-36-11 | D00323B | H05 | | | TB0133Z | 48 | BJ | | 150-199, 275-299 |
| 593R | 24 | PW | XR | | 0-0 | 31-36-11 | D00323B | G05 | | | TB0133Z | 47 | BJ | | ALL |
| 593Z | | | XR | | 0-0 | 31-36-11 | D00323B | DED | | | GDY0008 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 593Z | | | XR | | 0-0 | 31-36-11 | D00323B | DED | | | GDY0007 | S.. | 2 | | 150-154 |
| 594B | 24 | PW | XS | | 3-0 | 31-36-11 | D01769B | B10 | | | TB0133Z | 48 | BJ | | 050-099 |
| 594B | 24 | PW | XS | | 4-0 | 31-36-11 | D01769B | B10 | | | TB0133Z | 48 | BJ | | 150-199, 275-299 |
| 594R | 24 | PW | XS | | 0-0 | 31-36-11 | D01769B | A10 | | | TB0133Z | 47 | BJ | | ALL |
| 594Z | | | XS | | 0-0 | 31-36-11 | D01769B | DED | | | GDY0008 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 594Z | | | XS | | 0-0 | 31-36-11 | D01769B | DED | | | GDY0007 | S.. | 2 | | 150-154 |
| 595B | 24 | PW | XT | | 3-6 | 34-22-19 | D05201P | 17 | | | TB0133G | 153 | 2 | | 050-099 |
| 595B | 24 | PW | XT | | 5-0 | 34-22-19 | D05201P | 17 | | | TB0133G | 153 | 2 | | 150-199, 275-299 |
| 595R | 24 | PW | XT | | 0-0 | 34-22-19 | D05201P | 16 | | | TB0133G | 152 | 2 | | ALL |
| 595Z | | | XT | | 0-0 | 34-22-19 | D05201P | 18 | | | GDY0009 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 595Z | | | XT | | 0-0 | 34-22-19 | D05201P | 18 | | | GDY0008 | S.. | 2 | | 150-154 |
| 596B | 24 | PW | XU | | 4-0 | 23-22-11 | D04735P | 41 | | | TB0133Z | 62 | BJ | | 050-099 |
| 596B | 24 | PW | XU | | 5-0 | 23-22-11 | D04735P | 41 | | | TB0133Z | 62 | BJ | | 150-199, 275-299 |
| 596R | 24 | PW | XU | | 0-0 | 23-22-11 | D04735P | 38 | | | TB0133Z | 61 | BJ | | ALL |
| 596Z | | | XU | | 0-0 | 23-22-11 | D04735P | 40 | | | GDY0010 | S.. | 2 | | ALL |
| 597 | 20 | UA | | | 1-6 | 34-61-16 | D02275 | REF | | XV | GDX0012 | S.. | 2 | | ALL |
| 597B | 24 | PW | XV | | 3-3 | 34-61-16 | D02275 | B1 | | | D04429P | 18 | | | 050-099 |
| 597B | 24 | PW | XV | | 5-0 | 34-61-16 | D02275 | B1 | | | D04429P | 18 | | | 150-199, 275-299 |
| 597R | 24 | PW | XV | | 0-0 | 34-61-16 | D02275 | A1 | | | D04429P | 17 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 31
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|--|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | |
| 597Z | | | | XV | 0-0 | 34-61-16 | D02275 | REF | | | XV | D04429P | 19 | | | ALL |
| 598 | 20 | UA | | | 3-0 | 34-61-14 | D00323B | REF | | | XW | GDX0013 | S.. | 2 | | 150-154 |
| 598 | 20 | UA | | | 1-6 | 34-61-14 | GDX0013 | S.. | 2 | | | D00323B | REF | | XW | 277-299 |
| 598B | 24 | PW | XW | | 3-3 | 34-61-14 | D00323B | E09 | | | | TB0133Y | C077 | BJ | | 050-099 |
| 598B | 24 | PW | XW | | 4-0 | 34-61-14 | D00323B | E09 | | | | TB0133Y | C077 | BJ | | 150-199, 275-299 |
| 598R | 24 | PW | XW | | 0-0 | 34-61-14 | D00323B | D09 | | | | TB0133Y | A077 | BJ | | ALL |
| 598Z | | | | XW | 0-0 | 34-61-14 | GDY0012 | S.. | 2 | | | D00323B | DED | | | 050-099, 275-276 |
| 598Z | | | | XW | 0-0 | 34-61-14 | D00323B | REF | | | XW | TB0133Y | DED | | | 150-154 |
| 598Z | | | | XW | 0-0 | 34-61-14 | D00323B | DED | | | | GDY0012 | S.. | 2 | | 155-199 |
| 598Z | | | | XW | 0-0 | 34-61-14 | TB0133Y | DED | | | | D00323B | REF | | XW | 277-299 |
| 599B | 24 | PW | XX | | 4-9 | 34-61-14 | D04721P | 11 | | | | TB0133Y | C077 | BJ | | 050-099 |
| 599B | 24 | PW | XX | | 6-0 | 34-61-14 | TB0133Y | C077 | BJ | | | D04721P | 11 | | | 150-199 |
| 599B | 24 | PW | XX | | 6-0 | 34-61-14 | D04721P | 11 | | | | TB0133Y | C077 | BJ | | 275-299 |
| 599R | 24 | PW | XX | | 0-0 | 34-61-14 | D04721P | 10 | | | | TB0133Y | A077 | BJ | | 050-099, 275-299 |
| 599R | 24 | PW | XX | | 0-0 | 34-61-14 | TB0133Y | A077 | BJ | | | D04721P | 10 | | | 150-199 |
| 599Z | | | | XX | 0-0 | 34-61-14 | D04721P | 12 | | | | GDY0011 | S.. | 2 | | 050-099, 275-276 |
| 599Z | | | | XX | 0-0 | 34-61-14 | GDY0012 | S.. | 2 | | | D04721P | 12 | | | 150-154 |
| 599Z | | | | XX | 0-0 | 34-61-14 | GDY0011 | S.. | 2 | | | D04721P | 12 | | | 155-199 |
| 599Z | | | | XX | 0-0 | 34-61-14 | D04721P | 12 | | | | GDY0012 | S.. | 2 | | 277-299 |
| 601 | 24 | PK | | | 2-10 | 34-53-12 | D00331B | A01 | | | | D01423 | 1 | | | 050-099 |
| 601 | 24 | PK | | | 3-0 | 34-53-12 | D00331B | A01 | | | | D01423 | CAP | Y | | 150-199, 275-299 |
| 602 | 24 | PK | | | 2-10 | 34-53-12 | D00331B | B01 | | | | D01423 | 2 | | | 050-099 |
| 602 | 24 | PK | | | 3-0 | 34-53-12 | D00331B | B01 | | | | D01423 | 2 | | | 150, 152-199, 275-299 |
| 602 | 24 | PK | | | 3-0 | 34-53-12 | D00331B | B01 | | | | D01423 | CAP | Y | | 151 |
| 603 | 24 | PK | | | 2-10 | 34-53-12 | D00331B | C01 | | | | D01423 | 3 | | | 050-099 |
| 603 | 24 | PK | | | 3-0 | 34-53-12 | D00331B | C01 | | | | D01423 | CAP | Y | | 150-199, 275-299 |
| 604 | 24 | PK | | | 2-10 | 34-53-12 | D00331B | D01 | | | | D01423 | CAP | Y | | 050-099 |
| 604 | 24 | PK | | | 3-0 | 34-53-12 | D00331B | D01 | | | | D01423 | CAP | Y | | 150-199, 275-299 |
| 605 | 24 | PK | | | 2-10 | 34-53-12 | D00331B | E01 | | | | D01423 | CAP | Y | | 050-099 |
| 605 | 24 | PK | | | 3-0 | 34-53-12 | D00331B | E01 | | | | D01423 | CAP | Y | | 150-199 |
| 605 | 24 | PK | | | 3-0 | 34-53-12 | D00331B | E01 | | | | D01423 | 5 | | | 275-299 |
| 606 | 24 | PK | | | 2-10 | 34-53-12 | D00331B | F01 | | | | D01423 | 6 | | | 050-099 |
| 606 | 24 | PK | | | 3-0 | 34-53-12 | D00331B | F01 | | | | D01423 | 6 | | | 150-199 |
| 606 | 24 | PK | | | 3-0 | 34-53-12 | D00331B | F01 | | | | D01423 | CAP | Y | | 275-299 |
| 607 | 24 | PK | | | 2-10 | 34-53-12 | D00331B | G01 | | | | D01423 | CAP | Y | | 050-099 |
| 607 | 24 | PK | | | 3-0 | 34-53-12 | D00331B | G01 | | | | D01423 | 7 | | | 150-151, 153-154, 156-163, 165, 167-199 |
| 607 | 24 | PK | | | 3-0 | 34-53-12 | D00331B | G01 | | | | D01423 | CAP | Y | | 152, 155, 164, 166, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 32

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|--------|------|------|--------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 608 | 24 | | PK | | 2-10 | 34-53-12 | D00331B | | H01 | | D01423 | | CAP | Y | 050-099 |
| 608 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | H01 | | D01423 | | 8 | | 150-199 |
| 608 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | H01 | | D01423 | | CAP | Y | 275-299 |
| 609 | 24 | | PK | | 2-10 | 34-53-12 | D00331B | | J01 | | D01423 | | CAP | Y | 050-099 |
| 609 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | J01 | | D01423 | | 9 | | 150, 152-199 |
| 609 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | J01 | | D01423 | | CAP | Y | 151, 275-299 |
| 610 | 24 | | PK | | 2-10 | 34-53-12 | D00331B | | K01 | | D01423 | | 10 | | 050-099 |
| 610 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | K01 | | D01423 | | CAP | Y | 150, 152-199 |
| 610 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | K01 | | D01423 | | 10 | | 151, 275-299 |
| 611 | 24 | | PK | | 2-10 | 34-53-12 | D00331B | | A02 | | D01423 | | CAP | Y | 050-099 |
| 611 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | A02 | | D01423 | | CAP | Y | 150-151, 153-154, 156-163, 165, 167-199, 275-299 |
| 611 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | A02 | | D01423 | | 11 | | 152, 155, 164, 166 |
| 612 | 24 | | PK | | 2-10 | 34-53-12 | D00331B | | B02 | | D01423 | | CAP | Y | 050-099 |
| 612 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | B02 | | D01423 | | CAP | Y | 150-199, 275-299 |
| 613 | 24 | | PK | | 2-10 | 34-53-12 | D00331B | | C02 | | D01423 | | CAP | Y | 050-099 |
| 613 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | C02 | | D01423 | | CAP | Y | 150-151, 153-154, 156-163, 165, 167-199, 275-299 |
| 613 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | C02 | | D01423 | | 13 | | 152, 155, 164, 166 |
| 614 | 24 | | PK | | 2-10 | 34-53-12 | D00331B | | D02 | | D01423 | | 14 | | 050-099 |
| 614 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | D02 | | D01423 | | CAP | Y | 150-151, 153-154, 156-163, 165, 167-199, 275-299 |
| 614 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | D02 | | D01423 | | 14 | | 152, 155, 164, 166 |
| 615 | 24 | | PK | | 2-10 | 34-53-12 | D00331B | | E02 | | D01423 | | 15 | | 050-099 |
| 615 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | E02 | | D01423 | | CAP | Y | 150-164, 166-199, 275-299 |
| 615 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | E02 | | D01423 | | 15 | | 165 |
| 616 | 24 | | PK | | 2-10 | 34-53-12 | D00331B | | F02 | | D01423 | | CAP | Y | 050-099 |
| 616 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | F02 | | D01423 | | CAP | Y | 150-164, 166-199, 275-299 |
| 616 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | F02 | | D01423 | | 16 | | 165 |
| 617 | 24 | | PK | | 2-10 | 34-53-12 | D00331B | | G02 | | D01423 | | CAP | Y | 050-099 |
| 617 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | G02 | | D01423 | | CAP | Y | 150-151, 153-154, 156-163, 165, 275-299 |
| 617 | 24 | | PK | | 3-0 | 34-53-12 | D00331B | | G02 | | D01423 | | 17 | | 152, 155, 164, 166-199 |
| 618 | 24 | | PK | | 2-10 | 34-53-12 | D00331B | | H02 | | D01423 | | 18 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 33
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|--------|------|------|---|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | |
| 618 | 24 | | PK | 3-0 | 34-53-12 | D00331B | H02 | | | | D01423 | CAP | Y | 150-164, 166-199, 275-276 | | |
| 618 | 24 | | PK | 3-0 | 34-53-12 | D00331B | H02 | | | | D01423 | 18 | | 165, 277-299 | | |
| 619 | 24 | | PK | 2-10 | 34-53-12 | D00331B | J02 | | | | D01423 | CAP | Y | 050-099 | | |
| 619 | 24 | | PK | 3-0 | 34-53-12 | D00331B | J02 | | | | D01423 | 19 | | 150, 153-154, 156-157 | | |
| 619 | 24 | | PK | 3-0 | 34-53-12 | D00331B | J02 | | | | D01423 | CAP | Y | 151-152, 155, 162-199, 275-299 | | |
| 620 | 24 | | PK | 2-10 | 34-53-12 | D00331B | K02 | | | | D01423 | 20 | | 050-099 | | |
| 620 | 24 | | PK | 3-0 | 34-53-12 | D00331B | K02 | | | | D01423 | CAP | Y | 150-153, 155, 162-164, 166-199, 275-299 | | |
| 620 | 24 | | PK | 3-0 | 34-53-12 | D00331B | K02 | | | | D01423 | 20 | | 154, 156-157, 165 | | |
| 621 | 24 | | PK | 2-10 | 34-53-12 | D00331B | A03 | | | | D01423 | 21 | | 050-099 | | |
| 621 | 24 | | PK | 3-0 | 34-53-12 | D00331B | A03 | | | | D01423 | 21 | | 150, 152-153, 155, 162-199, 275-276, 278 | | |
| 621 | 24 | | PK | 3-0 | 34-53-12 | D00331B | A03 | | | | D01423 | CAP | Y | 151, 154, 156-157, 277, 280-299 | | |
| 622 | 24 | | PK | 2-10 | 34-53-12 | D00331B | B03 | | | | D01423 | CAP | Y | 050-099 | | |
| 622 | 24 | | PK | 3-0 | 34-53-12 | D00331B | B03 | | | | D01423 | 22 | | 150-151, 155, 162, 164-166, 277, 280-299 | | |
| 622 | 24 | | PK | 3-0 | 34-53-12 | D00331B | B03 | | | | D01423 | CAP | Y | 152-154, 156-157, 163, 167-199, 275-276, 278 | | |
| 623 | 24 | | PK | 2-10 | 34-53-12 | D00331B | C03 | | | | D01423 | CAP | Y | 050 | | |
| 623 | 24 | | PK | 2-10 | 34-53-12 | D00331B | C03 | | | | D01423 | 23 | | 051-099 | | |
| 623 | 24 | | PK | 3-0 | 34-53-12 | D00331B | C03 | | | | D01423 | 23 | | 150-151, 153, 157, 164, 280-299 | | |
| 623 | 24 | | PK | 3-0 | 34-53-12 | D00331B | C03 | | | | D01423 | CAP | Y | 152, 154-156, 162-163, 165-199, 275-278 | | |
| 624 | 24 | | PK | 2-10 | 34-53-12 | D00331B | D03 | | | | D01423 | 24 | | 050 | | |
| 624 | 24 | | PK | 2-10 | 34-53-12 | D00331B | D03 | | | | D01423 | CAP | Y | 051-099 | | |
| 624 | 24 | | PK | 3-0 | 34-53-12 | D00331B | D03 | | | | D01423 | 24 | | 150, 153, 156, 162, 165-166, 276-277, 280-299 | | |
| 624 | 24 | | PK | 3-0 | 34-53-12 | D00331B | D03 | | | | D01423 | CAP | Y | 151-152, 154-155, 157, 163-164, 167-199, 275, 278 | | |
| 625 | 24 | | PK | 2-10 | 34-53-12 | D00331B | E03 | | | | D01423 | 25 | | 050-099 | | |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 34
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 625 | 24 | | PK | 3-0 | 34-53-12 | D00331B | E03 | | | D01423 | 25 | | | 150-199, 275-299 | |
| 627 | 24 | | PK | 2-10 | 31-31-21 | D05203P | 18 | | | D05753J | 4 | | | 050-099 | |
| 627 | 24 | | PK | 3-0 | 31-31-21 | D05203P | 18 | | | D05753J | 4 | | | 150-199, 275-299 | |
| 628 | 24 | | PK | 2-10 | 31-31-21 | D05203P | 19 | | | D05753J | 5 | | | 050-099 | |
| 628 | 24 | | PK | 3-0 | 31-31-21 | D05203P | 19 | | | D05753J | 5 | | | 150-199, 275-299 | |
| 629 | 24 | | PK | 2-10 | 31-31-22 | D05203P | 37 | | | D05753J | 6 | | | 050-099 | |
| 629 | 24 | | PK | 3-0 | 31-31-22 | D05203P | 37 | | | D05753J | 6 | | | 150-199, 275-299 | |
| 634 | 22 | | PA | 2-11 | 31-35-11 | D05753J | 44 | | | TB0133G | 163 | 2 | | 050-099 | |
| 634 | 22 | | PA | 4-0 | 31-35-11 | D05753J | 44 | | | TB0133G | 163 | 2 | | 150-199, 275-299 | |
| 635 | 22 | | PA | 2-8 | 31-35-11 | D01769C | 1 | | | TB0133G | 163 | 2 | | 050-099 | |
| 635 | 22 | | PA | 4-0 | 31-35-11 | D01769C | 1 | | | TB0133G | 163 | 2 | | 150-199, 275-299 | |
| 643 | 22 | | PA | 2-4 | 31-35-11 | D01769A | J15 | | | GDX0008 | S.. | 2 | | 050-099 | |
| 643 | 22 | | PA | 3-0 | 31-35-11 | D01769A | J15 | | | GDX0008 | S.. | 2 | | 150-199, 275-299 | |
| 644 | 22 | | PA | 2-4 | 31-35-11 | D01769A | K15 | | | GDX0008 | S.. | 2 | | 050-099 | |
| 644 | 22 | | PA | 3-0 | 31-35-11 | D01769A | K15 | | | GDX0008 | S.. | 2 | | 150-199, 275-299 | |
| 645 | 20 | | PA | 2-4 | 31-35-11 | D01769C | 7 | | | GDX0008 | A.. | 2 | | 050-099 | |
| 645 | 20 | | PA | 3-0 | 31-35-11 | D01769C | 7 | | | GDX0008 | A.. | 2 | | 150-199, 275-299 | |
| 656 | 22 | | PA | 2-6 | 34-61-14 | D00323B | J15 | | | GDX0012 | D.. | 2 | | 050-099 | |
| 656 | 22 | | PA | 3-0 | 34-61-14 | D00323B | J15 | | | GDX0012 | D.. | 2 | | 150-156, 162-199 | |
| 656 | 22 | | PA | 3-0 | 34-61-13 | D00323B | J15 | | | GDX0012 | S.. | 2 | | 157 | |
| 661 | 24 | | PK | 3-9 | 34-53-12 | D00331A | C05 | | | TB0133Y | A041 | BJ | | 050-099 | |
| 661 | 24 | | PK | 5-0 | 34-53-12 | D00331A | C05 | | | TB0133Y | A041 | BJ | | 150-199 | |
| 661 | 24 | | PK | 4-0 | 34-53-12 | D00331A | C05 | | | TB0133Y | A041 | BJ | | 275-299 | |
| 665 | 24 | | PK | 2-10 | 31-35-16 | TB0133X | B148 | BJ | | TB0133X | C148 | BJ | | 050-099 | |
| 665 | 24 | | PK | 4-0 | 31-35-16 | TB0133X | B148 | BJ | | TB0133X | C148 | BJ | | 150-199, 275-299 | |
| 666 | 24 | | PK | 2-10 | 31-35-16 | TB0133X | D148 | BJ | | TB0133X | B149 | BJ | | 050-099 | |
| 666 | 24 | | PK | 4-0 | 31-35-16 | TB0133X | D148 | BJ | | TB0133X | B149 | BJ | | 150-199, 275-299 | |
| 668 | 24 | | PK | 2-11 | 31-31-22 | D04445P | 2 | | | D05703J | 30 | | | 050-099 | |
| 668 | 24 | | PK | 4-0 | 31-31-22 | D04445P | 2 | | | D05703J | 30 | | | 150-199, 275-299 | |
| 669 | 20 | | UA | 1-6 | 34-61-16 | TB0133Z | REF | | B9 | GDX0011 | S.. | 2 | | 050, 275-276 | |
| 669 | 20 | | UA | 1-6 | 34-61-16 | TB0133Z | REF | | B9 | GDX0012 | S.. | 2 | | 051-099, 155-199, 277-299 | |
| 669B | 24 | | PW | B9 | 3-0 | 34-61-16 | D04429P | 15 | | TB0133Z | 83 | BJ | | 050-099 | |
| 669B | 24 | | PW | B9 | 5-0 | 34-61-16 | D04429P | 15 | | TB0133Z | 83 | BJ | | 150-199, 275-299 | |
| 669R | 24 | | PW | B9 | 0-0 | 34-61-16 | D04429P | 14 | | TB0133Z | 82 | BJ | | ALL | |
| 669Z | | | | B9 | 0-0 | 34-61-16 | D04429P | 16 | | TB0133Z | REF | | B9 | 050-099, 155-199, 275-299 | |
| 669Z | | | | B9 | 0-0 | 34-61-16 | D04429P | 16 | | GDY0013 | S.. | 2 | | 150-154 | |
| 670 | 20 | | UA | 1-6 | 34-61-16 | D02279 | REF | | C0 | GDX0012 | S.. | 2 | | ALL | |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|---|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 670B | 24 | PW | C0 | | 2-5 | 34-61-16 | D02279 | | B1 | | D05733J | 8 | | | 050-099 |
| 670B | 24 | PW | C0 | | 4-0 | 34-61-16 | D02279 | | B1 | | D05733J | 8 | | | 150-199, 275-299 |
| 670R | 24 | PW | C0 | | 0-0 | 34-61-16 | D02279 | | A1 | | D05733J | 7 | | | ALL |
| 670Z | | | | | 0-0 | 34-61-16 | D02279 | | REF | C0 | D05733J | 9 | | | ALL |
| 671 | 20 | UA | | | 1-6 | 34-61-16 | D02275 | | REF | C1 | GDX0012 | S.. | 2 | | ALL |
| 671B | 24 | PW | C1 | | 2-5 | 34-61-16 | D02275 | | B3 | | D05733J | 11 | | | 050-099 |
| 671B | 24 | PW | C1 | | 4-0 | 34-61-16 | D02275 | | B3 | | D05733J | 11 | | | 150-199, 275-299 |
| 671R | 24 | PW | C1 | | 0-0 | 34-61-16 | D02275 | | A3 | | D05733J | 10 | | | ALL |
| 671Z | | | | | 0-0 | 34-61-16 | D02275 | | REF | C1 | D05733J | 12 | | | ALL |
| 673B | 24 | PW | C3 | | 3-1 | 34-46-11 | D04721P | | 2 | | TB0133Y | C129 | BJ | | 050-099 |
| 673B | 24 | PW | C3 | | 4-0 | 34-46-11 | D04721P | | 2 | | TB0133Y | C129 | BJ | | 150-199, 275-299 |
| 673R | 24 | PW | C3 | | 0-0 | 34-46-11 | D04721P | | 1 | | TB0133Y | A129 | BJ | | ALL |
| 673Z | | | | | 0-0 | 34-46-11 | D04721P | | 3 | | GDY0006 | S.. | 2 | | ALL |
| 674B | 24 | PW | C4 | | 3-1 | 34-61-15 | D04735P | | 20 | | TB0133Y | C130 | BJ | | 050-099 |
| 674B | 24 | PW | C4 | | 4-0 | 34-61-15 | D04735P | | 20 | | TB0133Y | C130 | BJ | | 150-199, 275-299 |
| 674R | 24 | PW | C4 | | 0-0 | 34-61-15 | D04735P | | 19 | | TB0133Y | A130 | BJ | | ALL |
| 674Z | | | | | 0-0 | 34-61-15 | D04735P | | 21 | | GDY0006 | S.. | 2 | | ALL |
| 676 | 24 | PV | C6 | | 5-4 | 34-61-16 | D04233P | | 3 | | TB0133Y | A078 | BJ | | 050-099 |
| 676 | 24 | PV | C6 | | 6-0 | 34-61-16 | D04233P | | 3 | | TB0133Y | A078 | BJ | | 150-156, 162-166 |
| 676 | 24 | PV | C6 | | 6-0 | 34-61-16 | D04233P | | 3 | | TB0133Z | 79 | BJ | | 157, 167-199, 275-299 |
| 676Z | | | | | 0-0 | 34-61-16 | D04233P | | DED | | TB0133Y | DED | | | 050-099, 150-156, 162-166, 275-276, 280-299 |
| 676Z | | | | C6 | 0-0 | 34-61-16 | D04233P | | DED | | TB0133Z | DED | | | 157, 167-199, 277-278 |
| 677 | 24 | PK | | | 4-0 | 34-61-16 | D02279 | | X1 | | TB0133Y | A078 | BJ | | 150-154 |
| 678 | 24 | PK | | | 4-1 | 34-61-16 | D02279 | | X2 | | D04445P | 15 | | | 050-099 |
| 678 | 24 | PK | | | 6-0 | 34-61-16 | D02279 | | X2 | | D04445P | 15 | | | 150-199, 275-299 |
| 679 | 24 | PK | | | 4-0 | 34-61-16 | D02275 | | X1 | | TB0133Y | A078 | BJ | | 150-154 |
| 680 | 24 | PK | | | 4-1 | 34-61-16 | D02275 | | X2 | | D04445P | 16 | | | 050-099 |
| 680 | 24 | PK | | | 6-0 | 34-61-16 | D02275 | | X2 | | D04445P | 16 | | | 150-199, 275-299 |
| 681 | 20 | UA | | | 1-6 | 34-61-16 | D02275 | | REF | D1 | GDX0012 | S.. | 2 | | ALL |
| 681B | 24 | PW | D1 | | 3-1 | 34-61-16 | D02275 | | B2 | | D05201P | 26 | | | 050-099 |
| 681B | 24 | PW | D1 | | 6-0 | 34-61-16 | D02275 | | B2 | | D05201P | 26 | | | 150-199, 275-299 |
| 681R | 24 | PW | D1 | | 0-0 | 34-61-16 | D02275 | | A2 | | D05201P | 25 | | | ALL |
| 681Z | | | | | 0-0 | 34-61-16 | D02275 | | REF | D1 | D05201P | 27 | | | ALL |
| 682B | 24 | PW | D2 | | 4-0 | 34-61-16 | D02279 | | B2 | | TB0133Y | C130 | BJ | | 050-099 |
| 682B | 24 | PW | D2 | | 5-0 | 34-61-16 | D02279 | | B2 | | TB0133Y | C130 | BJ | | 150-199, 275-299 |
| 682R | 24 | PW | D2 | | 0-0 | 34-61-16 | D02279 | | A2 | | TB0133Y | A130 | BJ | | ALL |
| 682Z | | | | | 0-0 | 34-61-16 | D02279 | | DED | | GDY0006 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 36

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------|----------|---------|------|------|--------|---------|---------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 684B | 24 | PW | D4 | | 5-0 | 34-61-11 | D04429P | | 3 | | TB0133G | 182 | 2 | | 150-199 |
| 684R | 24 | PW | D4 | | 0-0 | 34-61-11 | D04429P | | 2 | | TB0133G | 181 | 2 | | 150-199 |
| 684Z | | | D4 | | 0-0 | 34-61-11 | D04429P | | 1 | | GDY0013 | S.. | 2 | | 150-154 |
| 684Z | | | D4 | | 0-0 | 34-61-11 | D04429P | | 1 | | GDY0012 | S.. | 2 | | 155-199 |
| 686 | 22 | PA | | | 2-4 | 31-35-11 | D01769A | | G02 | | GDY0008 | S.. | 2 | | 050-099 |
| 686 | 22 | PA | | | 4-0 | 31-35-11 | D01769A | | G02 | | GDY0008 | S.. | 2 | | 150-199, 275-299 |
| 687 | 22 | PA | | | 2-4 | 31-35-11 | D01769B | | J15 | | GDY0008 | S.. | 2 | | 050-099 |
| 687 | 22 | PA | | | 4-0 | 31-35-11 | D01769B | | J15 | | GDY0008 | S.. | 2 | | 150-199, 275-299 |
| 689 | 22 | PA | | | 2-4 | 31-35-11 | D01769B | | K15 | | GDY0008 | S.. | 2 | | 050-099 |
| 689 | 22 | PA | | | 4-0 | 31-35-11 | D01769B | | K15 | | GDY0008 | S.. | 2 | | 150-199, 275-299 |
| 692 | 24 | PK | | | 4-7 | 34-53-11 | D00331B | | E06 | | TB0133H | 89 | 2 | | 050-099 |
| 692 | 24 | PK | | | 6-0 | 34-53-11 | D00331B | | E06 | | TB0133H | 89 | 2 | | 150-154 |
| 692 | 24 | PK | | | 5-0 | 34-53-11 | D00331B | | E06 | | TB0133H | 89 | 2 | | 155-199, 275-299 |
| 693 | 24 | PK | | | 3-9 | 34-53-12 | D00331B | | J05 | | TB0133Y | A041 | BJ | | 050-099 |
| 693 | 24 | PK | | | 5-0 | 34-53-12 | D00331B | | J05 | | TB0133Y | A041 | BJ | | 150-199 |
| 693 | 24 | PK | | | 4-0 | 34-53-12 | D00331B | | J05 | | TB0133Y | A041 | BJ | | 275-299 |
| 694 | 24 | PK | | | 3-9 | 34-53-12 | D00331A | | D05 | | TB0133Y | A041 | BJ | | 050-099 |
| 694 | 24 | PK | | | 5-0 | 34-53-12 | D00331A | | D05 | | TB0133Y | A041 | BJ | | 150-199 |
| 694 | 24 | PK | | | 4-0 | 34-53-12 | D00331A | | D05 | | TB0133Y | A041 | BJ | | 275-299 |
| 699 | 22 | PA | | | 5-0 | SPARE | D04681P | | 8 | | TB0133Y | A014 | BJ | | 153-154 |
| 710 | 24 | PK | | | 2-11 | 34-61-15 | D04445P | | 8 | | TB0133G | 103 | 2 | | 050-099 |
| 710 | 24 | PK | | | 4-0 | 34-61-15 | D04445P | | 8 | | TB0133G | 103 | 2 | | 150-199, 275-299 |
| 711 | 24 | PK | | | 6-0 | 34-61-15 | TB0133G | | 103 | 2 | D00323A | K13 | | | ALL |
| 717 | 20 | UA | | | 0-16 | 31-35-14 | D01769A | | REF | | H7 | GDY0010 | S.. | 2 | 050-099 |
| 717 | 20 | UA | | | 1-6 | 31-35-14 | D01769A | | REF | | H7 | GDY0008 | S.. | 2 | 150-154, 275-299 |
| 717 | 20 | UA | | | 1-6 | 31-35-14 | D01769A | | REF | | H7 | GDY0010 | S.. | 2 | 155-199 |
| 717B | 24 | PW | H7 | | 3-3 | 31-35-14 | D01769A | | F10 | | D04791P | 14 | | | 050-099 |
| 717B | 24 | PW | H7 | | 4-0 | 31-35-14 | D01769A | | F10 | | D04791P | 14 | | | 150-199, 275-299 |
| 717R | 24 | PW | H7 | | 0-0 | 31-35-14 | D01769A | | E10 | | D04791P | 13 | | | ALL |
| 717Z | | | H7 | | 0-0 | 31-35-14 | D01769A | | REF | | H7 | D04791P | 15 | | ALL |
| 719 | 24 | PK | | | 2-11 | 31-51-43 | D05733J | | 19 | | D05203P | 40 | | | 050-099 |
| 719 | 24 | PK | | | 4-0 | 31-51-43 | D05733J | | 19 | | D05203P | 40 | | | 150-199, 275-299 |
| 720 | 24 | PK | | | 2-11 | 31-51-41 | D05733J | | 21 | | D05203P | 4 | | | 050-099 |
| 720 | 24 | PK | | | 4-0 | 31-51-41 | D05733J | | 21 | | D05203P | 4 | | | 150-199, 275-299 |
| 721 | 24 | PK | | | 2-11 | 31-51-41 | D05733J | | 22 | | D05203P | 2 | | | 050-099 |
| 721 | 24 | PK | | | 4-0 | 31-51-41 | D05733J | | 22 | | D05203P | 2 | | | 150-199, 275-299 |
| 722 | 24 | PK | | | 2-11 | 31-51-41 | D05733J | | 23 | | D05203P | 3 | | | 050-099 |
| 722 | 24 | PK | | | 4-0 | 31-51-41 | D05733J | | 23 | | D05203P | 3 | | | 150-199, 275-299 |
| 723 | 24 | PK | | | 2-11 | 31-51-41 | D05733J | | 24 | | D05203P | 1 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 37

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|---|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | | | |
| 723 | 24 | | PK | | 4-0 | 31-51-41 | D05733J | | 24 | | | | | D05203P | 1 | | | 150-199, 275-299 |
| 724 | 24 | | PK | | 2-11 | 31-51-42 | D05733J | | 20 | | | | | D05203P | 5 | | | 050-099 |
| 724 | 24 | | PK | | 4-0 | 31-51-42 | D05733J | | 20 | | | | | D05203P | 5 | | | 150-199, 275-299 |
| 725 | 24 | | PK | | 4-2 | 34-16-11 | TB0133H | | 89 | 2 | | | | D05203P | 39 | | | 050-099 |
| 725 | 24 | | PK | | 5-0 | 34-16-11 | TB0133H | | 89 | 2 | | | | D05203P | 39 | | | 150-199, 275-299 |
| 726 | 24 | | PK | | 2-11 | 34-16-11 | D05733J | | 18 | | | | | D05203P | 6 | | | 050-099 |
| 726 | 24 | | PK | | 4-0 | 34-16-11 | D05733J | | 18 | | | | | D05203P | 6 | | | 150-199, 275-299 |
| 727 | 20 | | PA | | 2-9 | 34-61-13 | D05203P | | 31 | | | | | GDX0004 | D.. | 2 | | 050-099 |
| 727 | 20 | | PA | | 4-0 | 34-61-13 | D05203P | | 31 | | | | | GDX0004 | D.. | 2 | | 150-199, 275-299 |
| 728 | 22 | | PA | | 2-4 | 31-35-11 | D01769A | | H01 | | | | | GDX0008 | D.. | 2 | | 050-099 |
| 728 | 22 | | PA | | 3-0 | 31-35-11 | D01769A | | H01 | | | | | GDX0008 | S.. | 2 | | 150-199 |
| 728 | 22 | | PA | | 4-0 | 31-35-11 | D01769A | | H01 | | | | | GDX0008 | S.. | 2 | | 275-299 |
| 729 | 20 | | UA | | 2-4 | 31-35-15 | D01769B | | REF | | | 19 | | GDX0008 | S.. | 2 | | 050-099 |
| 729 | 20 | | UA | | 1-6 | 31-35-15 | D01769B | | REF | | | 19 | | GDX0008 | S.. | 2 | | 150-154, 275-299 |
| 729 | 20 | | UA | | 1-6 | 31-35-15 | D01769B | | REF | | | 19 | | GDX0010 | S.. | 2 | | 155-199 |
| 729B | 24 | | PW | 19 | 3-3 | 31-35-15 | D01769B | | F10 | | | | | D05703J | 39 | | | 050-099 |
| 729B | 24 | | PW | 19 | 5-0 | 31-35-15 | D01769B | | F10 | | | | | D05703J | 39 | | | 150-199, 275-299 |
| 729R | 24 | | PW | 19 | 0-0 | 31-35-15 | D01769B | | E10 | | | | | D05703J | 40 | | | ALL |
| 729Z | | | | 19 | 0-0 | 31-35-15 | D01769B | | REF | | | 19 | | D05703J | 41 | | | ALL |
| 730 | 24 | | PK | | 5-0 | 31-51-21 | D04868P | | 1 | | | | | D05203P | 11 | | | 150-154, 275 |
| 731 | 24 | | PK | | 5-0 | 31-51-21 | D04868P | | 2 | | | | | D05203P | 10 | | | 150-154, 275 |
| 732 | 24 | | PK | | 3-9 | 31-51-31 | D04868P | | 3 | | | | | D05203P | 8 | | | 050-099 |
| 732 | 24 | | PK | | 5-0 | 31-51-31 | D04868P | | 3 | | | | | D05203P | 8 | | | 150-156, 162-166, 275-276 |
| 732 | 24 | | PK | | 6-0 | 31-51-31 | D04868P | | 3 | | | | | TB0133D | C193 | 2 | | 157, 277-299 |
| 732 | 24 | | PK | | 6-0 | 31-51-31 | D04868P | | 3 | | | | | TB0133G | 91 | 2 | | 167-199 |
| 733 | 24 | | PK | | 5-0 | 31-51-33 | D04695P | | 15 | | | | | TB0133G | 27 | 2 | | 050-099 |
| 733 | 24 | | PK | | 4-0 | 31-51-33 | D04695P | | 15 | | | | | TB0133G | 27 | 2 | | 150-199, 275-299 |
| 734 | 24 | | PK | | 3-5 | 34-61-15 | D05733J | | 28 | | | | | D00323B | K07 | | | 050-099 |
| 734 | 24 | | PK | | 4-0 | 34-61-15 | D05733J | | 28 | | | | | D00323B | K07 | | | 150-199, 275-299 |
| 735 | 24 | | PK | | 2-11 | 31-41-16 | D05733J | | 35 | | | | | D05203P | 7 | | | 050-099 |
| 735 | 24 | | PK | | 4-0 | 31-41-16 | D05733J | | 35 | | | | | D05203P | 7 | | | 150-199, 275-299 |
| 736 | 24 | | PK | | 3-7 | 34-53-11 | D04695P | | 1 | | | | | D05733J | 36 | | | 050-099 |
| 736 | 24 | | PK | | 5-0 | 34-53-11 | D04695P | | 1 | | | | | D05733J | 36 | | | 150-199, 275-299 |
| 737 | 24 | | PK | | 2-11 | 31-51-41 | D05733J | | 37 | | | | | D05203P | 38 | | | 050-099 |
| 737 | 24 | | PK | | 4-0 | 31-51-41 | D05733J | | 37 | | | | | D05203P | 38 | | | 150-199, 275-299 |
| 746 | 22 | | PA | | 3-4 | 34-22-38 | D05733J | | 45 | | | | | D04151P | 36 | | | 050-099 |
| 746 | 22 | | PA | | 5-0 | 34-22-38 | D05733J | | 45 | | | | | D04151P | 36 | | | 150-199, 275-299 |
| 747 | 20 | | UA | | 1-6 | 34-61-16 | D00323B | | REF | | | K7 | | GDX0012 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 38

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 747B | 24 | PW | K7 | | 4-4 | 34-61-16 | D04429P | 21 | | | D00323B | H02 | | | 050-099 |
| 747B | 24 | PW | K7 | | 6-0 | 34-61-16 | D04429P | 21 | | | D00323B | H02 | | | 150-199, 275-299 |
| 747R | 24 | PW | K7 | | 0-0 | 34-61-16 | D04429P | 20 | | | D00323B | G02 | | | ALL |
| 747Z | | | | | 0-0 | 34-61-16 | D04429P | 22 | | | D00323B | REF | | K7 | ALL |
| 748 | 20 | UA | | | 1-6 | 34-45-12 | D00331B | REF | | K8 | GDX0003 | S.. | 2 | | 050-099, 155-156, 162-166 |
| 748 | 20 | UA | | | 1-6 | 34-45-12 | D00331A | REF | | K8 | GDX0003 | S.. | 2 | | 150-154, 157, 167-199, 275-299 |
| 748B | 24 | PW | K8 | | 3-11 | 34-45-12 | D04681P | 10 | | | D00331B | F05 | | | 050-099 |
| 748B | 24 | PW | K8 | | 5-0 | 34-45-12 | D04681P | 10 | | | D00331A | F05 | | | 150-152, 275-299 |
| 748B | 24 | PW | K8 | | 4-0 | 34-45-12 | D04681P | 10 | | | D00331A | F05 | | | 153-154, 157, 167-199 |
| 748B | 24 | PW | K8 | | 4-0 | 34-45-12 | D04681P | 10 | | | D00331B | F05 | | | 155-156, 162-166 |
| 748R | 24 | PW | K8 | | 0-0 | 34-45-12 | D04681P | 9 | | | D00331B | E05 | | | 050-099, 155-156, 162-166 |
| 748R | 24 | PW | K8 | | 0-0 | 34-45-12 | D04681P | 9 | | | D00331A | E05 | | | 150-154, 157, 167-199, 275-299 |
| 748Z | | | | | 0-0 | 34-45-12 | D04681P | 11 | | | D00331B | REF | | K8 | 050-099, 155-156, 162-166 |
| 748Z | | | | | 0-0 | 34-45-12 | D04681P | 11 | | | D00331A | REF | | K8 | 150-154, 157, 167-199, 275-299 |
| 749 | 20 | UA | | | 1-6 | 34-45-12 | D00331B | REF | | K9 | GDX0003 | S.. | 2 | | 050-099, 155-156, 162-166 |
| 749 | 20 | UA | | | 1-6 | 34-45-12 | D00331A | REF | | K9 | GDX0003 | S.. | 2 | | 150-154, 157, 167-199, 275-299 |
| 749B | 24 | PW | K9 | | 3-11 | 34-45-12 | D04681P | 13 | | | D00331B | H05 | | | 050-099 |
| 749B | 24 | PW | K9 | | 5-0 | 34-45-12 | D04681P | 13 | | | D00331A | H05 | | | 150-152, 275-299 |
| 749B | 24 | PW | K9 | | 4-0 | 34-45-12 | D04681P | 13 | | | D00331A | H05 | | | 153-154, 157, 167-199 |
| 749B | 24 | PW | K9 | | 4-0 | 34-45-12 | D04681P | 13 | | | D00331B | H05 | | | 155-156, 162-166 |
| 749R | 24 | PW | K9 | | 0-0 | 34-45-12 | D04681P | 12 | | | D00331B | G05 | | | 050-099, 155-156, 162-166 |
| 749R | 24 | PW | K9 | | 0-0 | 34-45-12 | D04681P | 12 | | | D00331A | G05 | | | 150-154, 157, 167-199, 275-299 |
| 749Z | | | | | 0-0 | 34-45-12 | D04681P | 14 | | | D00331B | REF | | K9 | 050-099, 155-156, 162-166 |
| 749Z | | | | | 0-0 | 34-45-12 | D04681P | 14 | | | D00331A | REF | | K9 | 150-154, 157, 167-199, 275-299 |
| 750 | 20 | UA | | | 1-6 | 34-45-14 | GDX0007 | S.. | 2 | | TB0133H | REF | | L0 | 050-099, 155-199, 275-299 |
| 750B | 24 | PW | L0 | | 3-6 | 34-45-14 | D04229P | 11 | | | TB0133H | 59 | 2 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 39
Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | |
| 750B | 24 | PW | L0 | 4-0 | 34-45-14 | D04229P | 11 | | | | TB0133H | 59 | 2 | | 150-152, 155-199, 275-299 | |
| 750B | 24 | PW | K0 | 4-0 | 34-45-14 | D04229P | 11 | | | | TB0133H | 59 | 2 | | 153-154 | |
| 750R | 24 | PW | L0 | 0-0 | 34-45-14 | D04229P | 10 | | | | TB0133H | 57 | 2 | | 050-099, 150-152, 155-199, 275-299 | |
| 750R | 24 | PW | K0 | 0-0 | 34-45-14 | D04229P | 10 | | | | TB0133H | 57 | 2 | | 153-154 | |
| 750Z | | | L0 | 0-0 | 34-45-14 | D04229P | 12 | | | | TB0133H | REF | | L0 | 050-099, 155-199, 275-299 | |
| 750Z | | | L0 | 0-0 | 34-45-14 | D04229P | 12 | | | | GDY0009 | S.. | 2 | | 150-152 | |
| 750Z | | | K0 | 0-0 | 34-45-14 | D04229P | 12 | | | | GDY0009 | S.. | 2 | | 153-154 | |
| 752 | 24 | PK | | 3-3 | 31-35-11 | D05703J | 43 | | | | D01769A | H02 | | | 050-099 | |
| 752 | 24 | PK | | 5-0 | 31-35-11 | D05703J | 43 | | | | D01769A | H02 | | | 150-199, 275-299 | |
| 753 | 22 | PA | | 4-5 | 31-35-17 | D01769B | F01 | | | | TB0133X | B105 | BJ | | 050-099 | |
| 753 | 22 | PA | | 6-0 | 31-35-17 | D01769B | F01 | | | | TB0133X | B105 | BJ | | 155-199, 275-299 | |
| 754 | 22 | PA | | 4-5 | 31-35-17 | D01769B | G01 | | | | TB0133X | D105 | BJ | | 050-099 | |
| 754 | 22 | PA | | 6-0 | 31-35-17 | D01769B | G01 | | | | TB0133X | D105 | BJ | | 150-199 | |
| 754 | 22 | PA | | 4-0 | 31-35-17 | D01769B | G01 | | | | TB0133X | D105 | BJ | | 275-299 | |
| 756 | 22 | PA | | 4-5 | 31-35-17 | D01769B | H01 | | | | TB0133X | B106 | BJ | | 050-099 | |
| 756 | 22 | PA | | 6-0 | 31-35-17 | D01769B | H01 | | | | TB0133X | B106 | BJ | | 150-199 | |
| 756 | 22 | PA | | 4-0 | 31-35-17 | D01769B | H01 | | | | TB0133X | B106 | BJ | | 275-299 | |
| 757 | 22 | PA | | 4-5 | 31-35-17 | D01769B | A03 | | | | TB0133X | D106 | BJ | | 050-099 | |
| 757 | 22 | PA | | 6-0 | 31-35-17 | D01769B | A03 | | | | TB0133X | D106 | BJ | | 150-199, 275-299 | |
| 758 | 22 | PA | | 4-5 | 31-35-17 | D01769B | E01 | | | | TB0133X | A105 | BJ | | 050-099 | |
| 758 | 22 | PA | | 6-0 | 31-35-17 | D01769B | E01 | | | | TB0133X | A105 | BJ | | 150-199, 275-299 | |
| 759 | 22 | PA | | 4-5 | 31-35-17 | D01769B | C02 | | | | TB0133X | C105 | BJ | | 050-099 | |
| 759 | 22 | PA | | 6-0 | 31-35-17 | D01769B | C02 | | | | TB0133X | C105 | BJ | | 150-199, 275-299 | |
| 760 | 22 | PA | | 4-5 | 31-35-17 | D01769B | D02 | | | | TB0133X | A106 | BJ | | 050-099 | |
| 760 | 22 | PA | | 6-0 | 31-35-17 | D01769B | D02 | | | | TB0133X | A106 | BJ | | 150-199, 275-299 | |
| 761 | 22 | PA | | 4-5 | 31-35-17 | D01769B | E02 | | | | TB0133X | C106 | BJ | | 050-099 | |
| 761 | 22 | PA | | 6-0 | 31-35-17 | D01769B | E02 | | | | TB0133X | C106 | BJ | | 150-199, 275-299 | |
| 763 | 22 | PA | | 2-10 | 31-35-17 | TB0133X | D105 | BJ | | | TB0133Z | 107 | BJ | | 050-099 | |
| 763 | 22 | PA | | 4-0 | 31-35-17 | TB0133X | D105 | BJ | | | TB0133Z | 107 | BJ | | 150-199, 275-299 | |
| 764 | 22 | PA | | 2-10 | 31-35-17 | TB0133X | B106 | BJ | | | TB0133Z | 107 | BJ | | 050-099 | |
| 764 | 22 | PA | | 4-0 | 31-35-17 | TB0133X | B106 | BJ | | | TB0133Z | 107 | BJ | | 150-199, 275-299 | |
| 765 | 22 | PA | | 3-0 | 31-35-17 | TB0133X | D106 | BJ | | | TB0133Z | 107 | BJ | | 167-199 | |
| 766 | 20 | PA | | 3-0 | 31-35-17 | TB0133Z | 107 | BJ | | | GDY0001 | S.. | 2 | | 050-099 | |
| 766 | 20 | PA | | 3-0 | 31-35-17 | TB0133Z | 107 | BJ | | | GDY0002 | S.. | 2 | | 150-199, 275-299 | |
| 775 | 20 | UA | | 4-0 | 34-61-11 | D00323A | REF | | N5 | | GDX0013 | S.. | 2 | | 150-154 | |
| 775B | 24 | PW | N5 | 3-4 | 34-61-11 | D00323A | E13 | | | | TB0133G | 182 | 2 | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 40

Jan 21/2005



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 775B | 24 | PW | N5 | 4-0 | 34-61-11 | D00323A | E13 | | | | TB0133G | 182 | 2 | | 150-199, 275-299 |
| 775R | 24 | PW | N5 | 0-0 | 34-61-11 | D00323A | D13 | | | | TB0133G | 181 | 2 | | ALL |
| 775Z | | | N5 | 0-0 | 34-61-11 | D00323A | DED | | | | GDY0012 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 775Z | | | N5 | 0-0 | 34-61-11 | D00323A | REF | | N5 | | TB0133G | DED | | | 150-154 |
| 776B | 24 | PW | N6 | 3-9 | 34-61-11 | D04429P | 3 | | | | TB0133G | 182 | 2 | | 050-099 |
| 776B | 24 | PW | N6 | 5-0 | 34-61-11 | D04429P | 3 | | | | TB0133G | 182 | 2 | | 275-299 |
| 776R | 24 | PW | N6 | 0-0 | 34-61-11 | D04429P | 2 | | | | TB0133G | 181 | 2 | | 050-099, 275-299 |
| 776Z | | | N6 | 0-0 | 34-61-11 | D04429P | 1 | | | | GDY0012 | S.. | 2 | | 050-099, 275-299 |
| 777B | 24 | PW | N7 | 3-1 | 23-22-15 | D04229P | 17 | | | | TB0133Z | 18 | BJ | | 050-099 |
| 777B | 24 | PW | N7 | 4-0 | 23-22-15 | D04229P | 17 | | | | TB0133Z | 18 | BJ | | 150-199, 275-299 |
| 777R | 24 | PW | N7 | 0-0 | 23-22-15 | D04229P | 16 | | | | TB0133Z | 17 | BJ | | ALL |
| 777Z | | | N7 | 0-0 | 23-22-15 | D04229P | 18 | | | | GDY0002 | S.. | 2 | | ALL |
| 778 | 24 | PK | | 3-5 | 34-61-15 | D05733J | 26 | | | | D00323B | G15 | | | 050-099 |
| 778 | 24 | PK | | 4-0 | 34-61-15 | D05733J | 26 | | | | D00323B | G15 | | | 150-199, 275-299 |
| 779 | 24 | PK | | 3-9 | 34-61-15 | D05733J | 27 | | | | TB0133Y | A019 | BJ | | 050-099 |
| 779 | 24 | PK | | 5-0 | 34-61-15 | D05733J | 27 | | | | TB0133Y | A019 | BJ | | 150-199, 275-299 |
| 780 | 24 | PK | | 5-4 | 34-61-15 | D00323B | A11 | | | | TB0133Y | A019 | BJ | | 050-099 |
| 780 | 24 | PK | | 6-0 | 34-61-15 | D00323B | A11 | | | | TB0133Y | A019 | BJ | | 150-199, 275-299 |
| 781 | 24 | PK | | 6-0 | 34-61-15 | D00323A | K08 | | | | TB0133Y | A019 | BJ | | ALL |
| 782 | 20 | UA | | 1-6 | 34-61-15 | D00323A | REF | | O2 | | GDY0013 | S.. | 2 | | ALL |
| 782B | 24 | PW | O2 | 3-5 | 34-61-15 | D05733J | 51 | | | | D00323A | H11 | | | 050-099 |
| 782B | 24 | PW | O2 | 4-0 | 34-61-15 | D05733J | 51 | | | | D00323A | H11 | | | 150-199, 275-299 |
| 782R | 24 | PW | O2 | 0-0 | 34-61-15 | D05733J | 50 | | | | D00323A | G11 | | | ALL |
| 782Z | | | O2 | 0-0 | 34-61-15 | D05733J | 52 | | | | D00323A | REF | | O2 | ALL |
| 783B | 24 | PW | O3 | 3-9 | 34-61-15 | D05733J | 54 | | | | TB0133Z | 18 | BJ | | 050-099 |
| 783B | 24 | PW | O3 | 5-0 | 34-61-15 | D05733J | 54 | | | | TB0133Z | 18 | BJ | | 150-199, 275-299 |
| 783R | 24 | PW | O3 | 0-0 | 34-61-15 | D05733J | 53 | | | | TB0133Z | 17 | BJ | | ALL |
| 783Z | | | O3 | 0-0 | 34-61-15 | D05733J | 55 | | | | GDY0002 | S.. | 2 | | ALL |
| 784B | 24 | PW | O4 | 6-0 | 34-61-15 | D00323A | E09 | | | | TB0133Z | 18 | BJ | | ALL |
| 784R | 24 | PW | O4 | 0-0 | 34-61-15 | D00323A | D09 | | | | TB0133Z | 17 | BJ | | ALL |
| 784Z | | | O4 | 0-0 | 34-61-15 | D00323A | DED | | | | GDY0002 | S.. | 2 | | ALL |
| 787 | 24 | PK | | 4-7 | 34-61-15 | D04791P | 23 | | | | TB0133D | C094 | 2 | | 050-099 |
| 787 | 24 | PK | | 5-0 | 34-61-15 | D04791P | 23 | | | | TB0133D | C094 | 2 | | 150-199, 275-299 |
| 788 | 24 | PK | | 3-9 | 34-61-15 | TB0133Y | A078 | BJ | | | TB0133D | A094 | 2 | | 050-099 |
| 788 | 24 | PK | | 4-0 | 34-61-15 | TB0133D | A094 | 2 | | | TB0133Y | A078 | BJ | | 150-156, 162-166 |
| 788 | 24 | PK | | 4-0 | 34-61-15 | TB0133D | A094 | 2 | | | TB0133Z | 79 | BJ | | 157, 167-199, 275-299 |
| 789 | 24 | PK | | 5-2 | 34-61-26 | D00323B | CAP | Y | | | D04445P | 10 | | | 050-099 |
| 789 | 24 | PK | | 6-0 | 34-61-26 | D04445P | 10 | | | | D00323B | CAP | Y | | 155-156, 162-166 |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|-------|---------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | | |
| 789 | 24 | | PK | 6-0 | 34-61-26 | D04445P | | 10 | | | | | D00323B | K09 | | | 157, 277-299 |
| 789 | 24 | | PK | 6-0 | 34-61-26 | D04445P | | 10 | | | | | D00323B | REF | ** | | 167-199 |
| 789 | 24 | | PK | 8-0 | 34-61-26 | D04445P | | 10 | | | | | D00323B | K09 | | | 275-276 |
| 790 | 24 | | PK | 5-2 | 34-61-16 | D04445P | | 9 | | | | | D00323B | CAP | Y | | 050-099 |
| 790 | 24 | | PK | 6-0 | 34-61-16 | D04445P | | 9 | | | | | D00323B | CAP | Y | | 155-156, 162-166 |
| 790 | 24 | | PK | 6-0 | 34-61-16 | D04445P | | 9 | | | | | D00323B | J09 | | | 157, 277-299 |
| 790 | 24 | | PK | 6-0 | 34-61-16 | D04445P | | 9 | | | | | D00323B | REF | ** | | 167-199 |
| 790 | 24 | | PK | 8-0 | 34-61-16 | D04445P | | 9 | | | | | D00323B | J09 | | | 275-276 |
| 791 | 22 | | PA | 2-10 | 31-35-17 | TB0133X | | C105 | BJ | | | | TB0133Z | 107 | BJ | | 050-099 |
| 791 | 22 | | PA | 3-0 | 31-35-17 | TB0133X | | C105 | BJ | | | | TB0133Z | 107 | BJ | | 150-199, 275-276 |
| 792 | 24 | | PK | 3-6 | 34-61-16 | D02279 | | X1 | | | | | TB0133D | C092 | 2 | | 050-099 |
| 792 | 24 | | PK | 4-0 | 34-61-16 | D02279 | | X1 | | | | | TB0133D | C092 | 2 | | 155-199, 275-299 |
| 793 | 24 | | PK | 3-9 | 34-61-16 | TB0133Y | | A078 | BJ | | | | TB0133D | A092 | 2 | | 050-099 |
| 793 | 24 | | PK | 4-0 | 34-61-16 | TB0133Y | | A078 | BJ | | | | TB0133D | A092 | 2 | | 155-156, 162-166 |
| 793 | 24 | | PK | 4-0 | 34-61-16 | TB0133Z | | 79 | BJ | | | | TB0133D | A092 | 2 | | 157, 167-199, 275-276 |
| 793 | 24 | | PK | 5-0 | 34-61-16 | TB0133Z | | 79 | BJ | | | | TB0133D | A092 | 2 | | 277-299 |
| 794 | 24 | | PK | 3-9 | 34-61-16 | TB0133Y | | A078 | BJ | | | | TB0133D | A093 | 2 | | 050-099 |
| 794 | 24 | | PK | 4-0 | 34-61-16 | TB0133Y | | A078 | BJ | | | | TB0133D | A093 | 2 | | 155-156, 162-166 |
| 794 | 24 | | PK | 4-0 | 34-61-16 | TB0133Z | | 79 | BJ | | | | TB0133D | A093 | 2 | | 157, 167-199, 275-276 |
| 794 | 24 | | PK | 5-0 | 34-61-16 | TB0133Z | | 79 | BJ | | | | TB0133D | A093 | 2 | | 277-299 |
| 795 | 24 | | PK | 3-9 | 34-61-16 | TB0133D | | C093 | 2 | | | | D02275 | X1 | | | 050-099 |
| 795 | 24 | | PK | 4-0 | 34-61-16 | D02275 | | X1 | | | | | TB0133D | C093 | 2 | | 155-199, 275-299 |
| 796 | 16 | | PA | 5-0 | 23-25-11 | D04217P | | 12 | FL | | | | D06151P | 21 | | | 156-157, 166-199, 277-299 |
| 797 | 24 | | PK | 3-5 | 34-61-14 | D00323A | | K06 | | | | | D05733J | 25 | | | 050-099 |
| 797 | 24 | | PK | 4-0 | 34-61-14 | D00323A | | K06 | | | | | D05733J | 25 | | | 150-199, 276-299 |
| 798 | 22 | | PA | 2-10 | 31-35-17 | TB0133X | | A105 | BJ | | | | TB0133Z | 107 | BJ | | 050-099 |
| 798 | 22 | | PA | 3-0 | 31-35-17 | TB0133X | | A105 | BJ | | | | TB0133Z | 107 | BJ | | 150-199, 275-299 |
| 799 | 22 | | PA | 2-10 | 31-35-17 | TB0133X | | A106 | BJ | | | | TB0133Z | 107 | BJ | | 050-099 |
| 799 | 22 | | PA | 3-0 | 31-35-17 | TB0133X | | A106 | BJ | | | | TB0133Z | 107 | BJ | | 150-199, 275-276 |
| 804B | 22 | | PR | Q4 | 4-0 | 23-25-13 | | D06151P | | 10 | | | TB0133Z | 62 | BJ | | 150, 153-155, 162-165 |
| 804B | 24 | | PW | Q4 | 4-0 | 23-25-13 | | D06151P | | 10 | | | TB0133Z | 62 | BJ | | 156-157, 166-199, 277-299 |
| 804R | 22 | | PR | Q4 | 0-0 | 23-25-13 | | D06151P | | 9 | | | TB0133Z | 61 | BJ | | 150, 153-155, 162-165 |
| 804R | 24 | | PW | Q4 | 0-0 | 23-25-13 | | D06151P | | 9 | | | TB0133Z | 61 | BJ | | 156-157, 166-199, 277-299 |
| 804Z | | | | Q4 | 0-0 | 23-25-13 | | D06151P | | 8 | | | GDY0010 | S.. | 2 | | 150, 153-199, 277-299 |
| 805B | 24 | | PW | Q5 | 4-0 | 23-25-13 | | D06151P | | 13 | | | D04717P | 14 | | | 156-157, 166-199, 277-278 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 42

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 805B | 24 | PW | Q5 | | 3-0 | 23-25-13 | D06151P | | 13 | | D04717P | | 14 | | 280-299 |
| 805R | 24 | PW | Q5 | | 0-0 | 23-25-13 | D06151P | | 12 | | D04717P | | 13 | | 156-157, 166-199, 277-299 |
| 805Z | | | Q5 | | 0-0 | 23-25-13 | D06151P | | 11 | | D04717P | | 12 | | 156-157, 166-199, 277-299 |
| 806B | 24 | PW | Q6 | | 3-0 | 23-25-13 | D06151P | | 16 | | D04429P | | 24 | | 156-157, 166-199, 277-299 |
| 806R | 24 | PW | Q6 | | 0-0 | 23-25-13 | D06151P | | 15 | | D04429P | | 23 | | 156-157, 166-199, 277-299 |
| 806Z | | | Q6 | | 0-0 | 23-25-13 | D06151P | | 14 | | D04429P | | 5 | | 156-157, 166-199, 277-299 |
| 809 | 24 | PK | | | 3-1 | 34-53-11 | D04695P | | 2 | | D00331A | B03 | | | 050-099 |
| 809 | 24 | PK | | | 4-0 | 34-53-11 | D04695P | | 2 | | D00331A | B03 | | | 150-152, 155-199, 275-299 |
| 821 | 24 | PK | | | 3-0 | 34-61-17 | D00323B | K13 | ** | | D06199J | | 2 | | 157 |
| 821 | 24 | PK | | | 3-0 | 34-61-17 | D00323B | REF | ** | | D06199J | | 2 | | 167-199 |
| 821 | 24 | PK | | | 3-0 | 34-61-17 | D00323B | K13 | | | D06199J | | 2 | | 277-299 |
| 822 | 24 | PK | | | 4-0 | 34-61-27 | D06199J | | 1 | | TB0133G | 91 | 2 | | 157, 167-199, 277-299 |
| 823 | 24 | PK | | | 3-6 | 34-61-27 | TB0133D | A192 | 2 | | TB0133G | 91 | 2 | | 157, 167-199 |
| 823 | 24 | PK | | | 4-0 | 34-61-27 | TB0133D | A192 | 2 | | TB0133G | 91 | 2 | | 277-299 |
| 824 | 24 | PK | | | 5-0 | 34-61-27 | TB0133D | C192 | 2 | | D00323A | K15 | | | 157, 167-199 |
| 824 | 24 | PK | | | 4-0 | 34-61-27 | TB0133D | C192 | 2 | | D00323A | K15 | | | 277-299 |
| 827 | 24 | PK | | | 5-0 | 31-51-31 | D05203P | | 8 | | TB0133D | A193 | 2 | | 157, 277-299 |
| 827 | 24 | PK | | | 5-0 | 31-51-31 | D05203P | | 8 | | TB0133G | 91 | 2 | | 167-199 |
| 828 | 24 | PK | | | 4-0 | 34-61-27 | D06199J | | 7 | | TB0133D | A095 | 2 | | 157, 167-199, 277-299 |
| 828 | 24 | PK | | | 6-0 | 34-61-27 | D06199J | | 7 | | TB0133D | A095 | 2 | | 275-276 |
| 829 | 24 | PK | | | 6-0 | 34-61-17 | D02817 | X1 | | | TB0133Z | 79 | ** | | 157 |
| 829 | 24 | PK | | | 6-0 | 34-61-17 | D02817 | X1 | | | TB0133Z | 79 | % | | 167-199 |
| 829 | 24 | PK | | | 8-0 | 34-61-17 | D02817 | X1 | | | TB0133Z | 79 | BJ | | 275-276 |
| 829 | 24 | PK | | | 6-0 | 34-61-17 | D02817 | X1 | | | TB0133Z | 79 | BJ | | 277-278 |
| 829 | 24 | PK | | | 5-0 | 34-61-17 | D02817 | X1 | | | TB0133Z | 79 | BJ | | 280-299 |
| 830 | 24 | PK | | | 4-0 | 34-61-17 | D02817 | X2 | | | TB0133D | A095 | 2 | | 157, 167-199 |
| 830 | 24 | PK | | | 9-0 | 34-61-17 | D02817 | X2 | | | TB0133D | A095 | 2 | | 275-276 |
| 830 | 24 | PK | | | 6-0 | 34-61-17 | D02817 | X2 | | | TB0133D | A095 | 2 | | 277-299 |
| 831 | 24 | PK | | | 4-0 | 34-61-17 | D00323B | K06 | | | TB0133D | C095 | 2 | | 157, 167-199, 277-299 |
| 831 | 24 | PK | | | 6-0 | 34-61-17 | D00323B | K06 | | | TB0133D | C095 | 2 | | 275-276 |
| 832 | 24 | PK | | | 4-0 | 34-61-17 | D00323B | K04 | | | TB0133D | C096 | 2 | | 157, 167-199, 277-299 |
| 832 | 24 | PK | | | 6-0 | 34-61-17 | D00323B | K04 | | | TB0133D | C096 | 2 | | 275-276 |
| 833 | 24 | PK | | | 4-0 | 34-61-17 | D06199J | | 6 | | TB0133D | A096 | 2 | | 157, 167-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 43
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|-----------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | | | |
| 833 | 24 | | PK | | 6-0 | 34-61-17 | D06199J | | 6 | | | | TB0133D | A096 | 2 | | 275-276 |
| 834B | 24 | | PW | T4 | 5-0 | 34-61-17 | D02817 | | B3 | | | | TB0133Z | 155 | BJ | | 157, 167-199, 277-278 |
| 834B | 24 | | PW | T4 | 7-0 | 34-61-17 | D02817 | | B3 | | | | TB0133Z | 155 | BJ | | 275-276 |
| 834B | 24 | | PW | T4 | 4-0 | 34-61-17 | D02817 | | B3 | | | | TB0133Z | 155 | BJ | | 280-299 |
| 834R | 24 | | PW | T4 | 0-0 | 34-61-17 | D02817 | | A3 | | | | TB0133Z | 154 | BJ | | 157, 167-199, 275-299 |
| 834Z | | | | T4 | 0-0 | 34-61-17 | D02817 | | DED | | | | GDY0009 | S.. | 2 | | 157, 167-199, 275-299 |
| 836B | 24 | | PW | T6 | 4-0 | 34-61-17 | D02817 | | B1 | | | | TB0133Z | 23 | BJ | | 157, 167-199, 275-299 |
| 836R | 24 | | PW | T6 | 0-0 | 34-61-17 | D02817 | | A1 | | | | TB0133Z | 24 | BJ | | 157, 167-199, 275-299 |
| 836Z | | | | T6 | 0-0 | 34-61-17 | D02817 | | DED | | | | GDY0003 | S.. | 2 | | 157, 167-199, 275-299 |
| 837 | 20 | | UA | | 1-6 | 34-22-81 | GDX0001 | | S.. | 2 | | | D02817 | REF | | T7 | 157, 167-199 |
| 837 | 20 | | UA | | 1-6 | 34-22-81 | GDX0004 | | S.. | 2 | | | D02817 | REF | | T7 | 275-299 |
| 837B | 24 | | PW | T7 | 4-0 | 34-22-81 | D04445P | | 19 | | | | D02817 | B2 | | | 157, 167-199, 277-299 |
| 837B | 24 | | PW | T7 | 6-0 | 34-22-81 | D04445P | | 19 | | | | D02817 | B2 | | | 275-276 |
| 837R | 24 | | PW | T7 | 0-0 | 34-22-81 | D04445P | | 18 | | | | D02817 | A2 | | | 157, 167-199, 275-299 |
| 837Z | | | | T7 | 0-0 | 34-22-81 | D04445P | | 20 | | | | D02817 | REF | | T7 | 157, 167-199, 275-299 |
| 840 | 24 | | PK | | 5-0 | 34-61-27 | D06199J | | 11 | | | | TB0133Z | 79 | BJ | | 157, 167-199, 275-299 |
| 842 | 24 | | PK | | 4-0 | 34-53-11 | D04695P | | 16 | | | | D00331A | K05 | | | 157, 167-199, 277-299 |
| 844 | 20 | | PA | | 2-6 | 34-53-11 | D00331C | | 8 | | | | GDX0003 | D.. | 2 | | 157, 167-199, 277-299 |
| 845B | 24 | | PW | U5 | 6-0 | 34-61-15 | TB0133Y | | C003 | BJ | | | TB0133Z | 81 | BJ | | 157, 167-199 |
| 845R | 24 | | PW | U5 | 0-0 | 34-61-15 | TB0133Y | | A003 | BJ | | | TB0133Z | 80 | BJ | | 157, 167-199 |
| 845Z | | | | U5 | 0-0 | 34-61-15 | GDY0001 | | S.. | 2 | | | TB0133Z | DED | | | 157, 167-199 |
| 848 | 24 | | PK | | 5-0 | 34-61-27 | TB0133G | | 91 | 2 | | | TB0133D | A193 | 2 | | 157, 277-299 |
| 874 | 22 | | PA | | 3-0 | 34-61-13 | D00323B | | K14 | | | | GDX0012 | S.. | 2 | | 157, 167-199, 277-299 |
| 874 | 22 | | PA | | 4-0 | 34-61-13 | D00323B | | K14 | | | | GDX0012 | S.. | 2 | | 275-276 |
| 900 | 20 | | PA | | 4-0 | 34-53-11 | D00331A | | | | AA | | GDX0003 | S.. | 2 | | 275-299 |
| 901 | 20 | | PA | | 4-0 | 34-53-11 | D00331B | | G05 | DL | | | GDX0003 | D.. | 2 | | 275-299 |
| 901B | 22 | | PR | HX | 5-0 | 23-25-13 | D04229P | | 23 | | | | TB0133Z | 18 | BJ | | 150, 153-199 |
| 901R | 22 | | PR | HX | 0-0 | 23-25-13 | D04229P | | 22 | | | | TB0133Z | 17 | BJ | | 150, 153-199 |
| 901Z | | | | HX | 0-0 | 23-25-13 | D04229P | | 24 | | | | GDY0002 | S.. | 2 | | 150, 153-199 |
| 902 | 20 | | PA | | 3-0 | 34-53-11 | D00331A | | | | AB | | GDX0003 | S.. | 2 | | 275-299 |
| 902B | 24 | | PW | AC | 0-0 | 34-53-11 | D00331A | | B06 | | | | TB0133Z | 23 | BJ | | 275-299 |
| 902R | 24 | | PW | AC | 10-0 | 34-53-11 | D00331A | | A06 | | | | TB0133Z | 24 | BJ | | 275-299 |
| 902Z | | | | AC | 0-0 | 34-53-11 | D00331A | | | | AA | | GDY0002 | S.. | 2 | | 275-276 |
| 902Z | | | | AC | 0-0 | 34-53-11 | D00331A | | | | AA | | GDY0003 | S.. | 2 | | 277-299 |
| 903 | 20 | | PA | | 3-0 | 34-53-11 | D00331A | | | | AC | | GDX0003 | S.. | 2 | | 275-299 |
| 904B | 24 | | PW | AD | 0-0 | 34-53-11 | D00331A | | D02 | | | | D04791P | 16 | | | 275-299 |
| 904R | 24 | | PW | AD | 5-0 | 34-53-11 | D00331A | | C02 | | | | D04791P | 12 | | | 275-299 |
| 904Z | | | | AD | 0-0 | 34-53-11 | D00331A | | | | AB | | D04791P | 24 | | | 275-299 |
| 905B | 24 | | PW | AH | 0-0 | 34-53-11 | D00331A | | B07 | | | | D05203P | 14 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 44

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0133 | 286T0133 | | | E2-2 L,SHELF (continued) | | | | | | | | | | | |
| 905R | 24 | | PW | AH | 5-0 | 34-53-11 | D00331A | A07 | | | D05203P | 13 | | | 275-299 |
| 905Z | | | | AH | 0-0 | 34-53-11 | D00331A | | | AC | D05203P | 9 | | | 275 |
| 905Z | | | | AH | 0-0 | 34-53-11 | D00331A | | | AC | D05203P | 11 | | | 276-299 |
| W0135 | 286T0135 | | | E2-3 L SHELF | | | | | | | | | | | |
| 001 | 24 | | PK | | 4-0 | 34-61-23 | D05703P | | 11 | | TB0145X | A160 | BJ | | ALL |
| 002 | 22 | | PA | | 4-0 | 34-22-17 | D05703P | | 34 | | TB0145Y | A139 | BJ | | ALL |
| 005 | 22 | | PQ | AE | 4-0 | 31-31-11 | D00327D | | H07 | | TB0145X | A146 | BJ | | ALL |
| 005Z | | | | AE | 0-0 | 31-31-11 | D00327D | | DED | | TB0145X | DED | | | ALL |
| 006 | 22 | | PA | | 4-0 | 31-31-11 | D04711P | | 8 | | D00327A | G07 | | | ALL |
| 007 | 24 | | PK | | 4-0 | 34-61-23 | D05703P | | 18 | | TB0145X | A158 | BJ | | ALL |
| 008 | 24 | | PK | | 5-0 | 31-31-11 | TB0145D | | C127 | 2 | TB0145Y | C155 | BJ | | 050-099, 150-199, 275-276 |
| 008 | 24 | | PK | | 5-0 | 31-31-11 | TB0145D | | C191 | 2 | TB0145Y | C155 | BJ | | 277-299 |
| 012 | 24 | | PK | | 4-0 | 31-31-13 | TB0145Z | | 138 | BJ | D04711P | 12 | | | ALL |
| 013 | 24 | | PK | | 4-0 | 31-31-13 | TB0145Y | | C155 | BJ | D04711P | 13 | | | ALL |
| 018 | 24 | | PK | | 5-0 | 34-12-12 | D05207P | | 18 | | TB0145X | B158 | BJ | | ALL |
| 01GB | 24 | | PW | G | 3-3 | 34-12-61 | D05229P | | 14 | | TB0145Z | 62 | BJ | | 050-099, 152 |
| 01GB | 24 | | PW | G | 3-3 | 34-12-61 | D05229P | | 15 | | TB0145Z | 62 | BJ | | 150-151, 153-199, 275-299 |
| 01GR | 24 | | PW | G | 0-0 | 34-12-61 | D05229P | | 15 | | TB0145Z | 61 | BJ | | 050-099, 152 |
| 01GR | 24 | | PW | G | 0-0 | 34-12-61 | D05229P | | 16 | | TB0145Z | 61 | BJ | | 150-151, 153-199, 275-299 |
| 01GZ | | | | G | 0-0 | 34-12-61 | D05229P | | 16 | | GDY0010 | S.. | 2 | | 050-099 |
| 01GZ | | | | G | 0-0 | 34-12-61 | D05229P | | 17 | | GDY0010 | S.. | 2 | | 150-151, 153-199, 275-299 |
| 01GZ | | | | G | 0-0 | 34-12-61 | D05229P | | 16 | | GDY0013 | S.. | 2 | | 152 |
| 01H | 24 | | PK | | 3-9 | 34-12-61 | D05229P | | 13 | | TB0145Y | C136 | BJ | | 050-099 |
| 01H | 24 | | PK | | 3-9 | 34-12-61 | D05229P | | 14 | | TB0145Y | C032 | BJ | | 150-151, 153-199, 275-299 |
| 01H | 24 | | PK | | 3-9 | 34-12-61 | D05229P | | 13 | | TB0145Y | C030 | BJ | | 152 |
| 011 | 24 | | PK | | 3-9 | 34-12-61 | D05229P | | 11 | | TB0145Y | A194 | BJ | | 050-099, 152 |
| 011 | 24 | | PK | | 3-9 | 34-12-61 | D05229P | | 12 | | TB0145Y | A185 | BJ | | 150-151, 153-199, 275-299 |
| 01J | 24 | | PK | | 3-9 | 34-12-61 | D05229P | | 12 | | TB0145Y | C194 | BJ | | 050-099, 152 |
| 01J | 24 | | PK | | 3-9 | 34-12-61 | D05229P | | 13 | | TB0145Y | C185 | BJ | | 150-151, 153-199, 275-299 |
| 020 | 24 | | PK | | 4-0 | 31-31-11 | TB0145Y | | C155 | BJ | D00327A | A11 | | | ALL |
| 021 | 24 | | PK | | 5-0 | 31-31-11 | D04725P | | 21 | | D00327A | G15 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 45
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | |
| 022 | 22 | | PA | 4-0 | 31-31-11 | TB0145Z | 132 | BJ | | | | | D00327C | 1 | | ALL |
| 025 | 22 | | PA | 3-0 | 31-31-11 | GDX0008 | D.. | 2 | | | | | D00327D | J15 | | ALL |
| 026 | 22 | | PA | 3-0 | 31-31-11 | GDX0008 | D.. | 2 | | | | | D00327D | K15 | | ALL |
| 027 | 20 | | PA | 3-0 | 31-31-11 | GDX0008 | A.. | 2 | | | | | D00327C | 7 | | ALL |
| 028 | 22 | | PA | 3-0 | 31-31-11 | GDX0008 | D.. | 2 | | | | | D00327A | K15 | | ALL |
| 029 | 22 | | PA | 3-0 | 31-31-11 | GDX0008 | D.. | 2 | | | | | D00327A | J15 | | ALL |
| 030 | 24 | | PK | 6-0 | 31-31-11 | D00327A | B11 | | | | | | D04741P | 12 | | ALL |
| 035 | 22 | | PA | 4-0 | 31-31-18 | TB0145R | A120 | 2 | | | | | TB0145R | A117 | 2 | 050-099, 150-199, 275-276 |
| 035 | 22 | | PA | 3-0 | 31-31-18 | TB0145R | A193 | 2 | | | | | TB0145R | A192 | 2 | 277, 280-299 |
| 035 | 22 | | PA | 5-0 | 31-31-18 | TB0145R | A193 | 2 | | | | | TB0145R | A087 | 2 | 278 |
| 036 | 22 | | PA | 4-0 | 31-31-18 | TB0145R | A121 | 2 | | | | | TB0145R | A120 | 2 | 050-099, 150-199, 275-276 |
| 036 | 22 | | PA | 3-0 | 31-31-18 | TB0145R | A194 | 2 | | | | | TB0145R | A193 | 2 | 277-299 |
| 037 | 22 | | PA | 4-0 | 31-31-18 | TB0145R | A122 | 2 | | | | | TB0145R | A121 | 2 | 050-099, 150-199, 275-276 |
| 037 | 22 | | PA | 3-0 | 31-31-18 | TB0145R | A195 | 2 | | | | | TB0145R | A194 | 2 | 277-299 |
| 038 | 22 | | PA | 4-0 | 31-31-18 | TB0145R | A123 | 2 | | | | | TB0145R | A122 | 2 | 050-099, 150-199, 275-276 |
| 038 | 22 | | PA | 3-0 | 31-31-18 | TB0145R | A196 | 2 | | | | | TB0145R | A195 | 2 | 277-299 |
| 039 | 22 | | PA | 4-0 | 31-31-18 | TB0145R | C123 | 2 | | | | | D05225P | 1 | | 050-099, 150-199, 275-276 |
| 039 | 22 | | PA | 7-0 | 31-31-18 | TB0145R | C196 | 2 | | | | | D05225P | 1 | | 277-299 |
| 040 | 22 | | PA | 4-0 | 31-31-18 | TB0145R | C122 | 2 | | | | | D05225P | 2 | | 050-099, 150-199, 275-276 |
| 040 | 22 | | PA | 7-0 | 31-31-18 | TB0145R | C195 | 2 | | | | | D05225P | 2 | | 277-278 |
| 040 | 22 | | PA | 8-0 | 31-31-18 | TB0145R | C195 | 2 | | | | | D05225P | 2 | | 280-299 |
| 041 | 22 | | PA | 4-0 | 31-31-18 | TB0145R | C121 | 2 | | | | | D05225P | 3 | | 050-099, 150-199, 275-276 |
| 041 | 22 | | PA | 7-0 | 31-31-18 | TB0145R | C194 | 2 | | | | | D05225P | 3 | | 277-299 |
| 042 | 22 | | PA | 4-0 | 31-31-18 | TB0145R | C120 | 2 | | | | | D05225P | 4 | | 050-099, 150-199, 275-276 |
| 042 | 22 | | PA | 7-0 | 31-31-18 | TB0145R | C193 | 2 | | | | | D05225P | 4 | | 277-299 |
| 043 | 22 | | PA | 4-0 | 31-31-18 | TB0145R | C117 | 2 | | | | | D05225P | 5 | | 050-099, 150-199, 275-276 |
| 043 | 22 | | PA | 7-0 | 31-31-18 | TB0145R | C192 | 2 | | | | | D05225P | 5 | | 277, 280-299 |
| 043 | 22 | | PA | 6-0 | 31-31-18 | TB0145R | C087 | 2 | | | | | D05225P | 5 | | 278 |
| 044 | 22 | | PA | 4-0 | 31-31-18 | TB0145R | C116 | 2 | | | | | D05225P | 6 | | 050-099, 150-199, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 46

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | |
| 044 | 22 | | PA | | 7-0 | 31-31-18 | TB0145R | C095 | 2 | | D05225P | | 6 | | 277-299 |
| 045 | 24 | | PK | | 3-0 | 31-31-18 | D05733P | | 15 | | D00327D | | B05 | | ALL |
| 046 | 24 | | PK | | 5-0 | 31-31-18 | D05733P | | 16 | | D00327D | | D03 | | ALL |
| 047 | 24 | | PK | | 3-0 | 31-31-18 | D05733P | | 17 | | D00327A | | C03 | | ALL |
| 050 | 24 | | PK | | 4-0 | 31-31-12 | TB0145Y | A139 | BJ | | D00327A | | F03 | | ALL |
| 051 | 22 | | PA | | 4-0 | 31-31-18 | TB0145R | A117 | 2 | | TB0145R | A116 | 2 | | 050-099, 150-199, 275-276 |
| 051 | 22 | | PA | | 3-0 | 31-31-18 | TB0145R | A192 | 2 | | TB0145R | A095 | 2 | | 277 |
| 051 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | A087 | 2 | | TB0145R | A095 | 2 | | 278 |
| 051 | 22 | | PA | | 2-0 | 31-31-18 | TB0145R | A192 | 2 | | TB0145R | A095 | 2 | | 280-299 |
| 052 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | A116 | 2 | | TB0145Z | | 131 | BJ | 050-099, 150-199, 275-276 |
| 052 | 22 | | PA | | 6-0 | 31-31-18 | TB0145R | A095 | 2 | | TB0145Z | | 131 | BJ | 277-299 |
| 053 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C123 | 2 | | D00327A | | K05 | | 050-099, 150-199, 275-276 |
| 053 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C196 | 2 | | D00327A | | K05 | | 277-299 |
| 054 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C122 | 2 | | D00327A | | J05 | | 050-099, 150-199, 275-276 |
| 054 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C195 | 2 | | D00327A | | J05 | | 277-299 |
| 055 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C121 | 2 | | D00327A | | H05 | | 050-099, 150-199, 275-276 |
| 055 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C194 | 2 | | D00327A | | H05 | | 277-299 |
| 056 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C120 | 2 | | D00327D | | K05 | | 050-099, 150-199, 275-276 |
| 056 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C193 | 2 | | D00327D | | K05 | | 277-299 |
| 057 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C117 | 2 | | D00327D | | J05 | | 050-099, 150-199, 275-276 |
| 057 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C192 | 2 | | D00327D | | J05 | | 277, 280-299 |
| 057 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C087 | 2 | | D00327D | | J05 | | 278 |
| 058 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C116 | 2 | | D00327D | | H05 | | 050-099, 150-199, 275-276 |
| 058 | 22 | | PA | | 5-0 | 31-31-18 | TB0145R | C095 | 2 | | D00327D | | H05 | | 277-299 |
| 059 | 22 | | PA | | 3-0 | 31-31-13 | GDX0007 | A.. | 2 | | D00327B | | B11 | | ALL |
| 05A | 24 | | PK | | 4-0 | 34-61-27 | D06199P | | 11 | | TB0145X | C089 | BJ | | 157, 167-199 |
| 05A | 24 | | PK | | 7-0 | 34-61-27 | D06199P | | 11 | | TB0145X | A008 | BJ | | 275-276 |
| 05A | 24 | | PK | | 6-0 | 34-61-27 | D06199P | | 11 | | TB0145X | A008 | BJ | | 277-299 |
| 060 | 24 | | PK | | 4-0 | 34-61-17 | D06199P | | 2 | | TB0145Y | A078 | BJ | | 157, 167-199 |
| 060 | 24 | | PK | | 6-0 | 34-61-17 | D06199P | | 2 | | TB0145Y | C012 | BJ | | 277-299 |
| 061 | 24 | | PK | | 4-0 | 31-31-13 | D04711P | | 18 | | D00327B | | H04 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 47
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | |
| 062 | 22 | | PA | | 3-0 | 31-31-13 | GDX0007 | A.. | 2 | | D00327E | B08 | | | ALL |
| 064 | 24 | | PK | | 7-0 | 31-31-11 | TB0145D | A127 | 2 | | D04725P | 6 | | | 050-099, 150-199, 275-276 |
| 064 | 24 | | PK | | 4-0 | 31-31-11 | TB0145D | A191 | 2 | | D04725P | 6 | | | 277-299 |
| 073 | 22 | | PA | | 5-0 | 31-31-11 | D04215P | | 3 | | TB0145Z | 138 | BJ | | ALL |
| 074 | 22 | | PA | | 5-0 | 31-31-11 | D04215P | | 4 | | TB0145Z | 132 | BJ | | ALL |
| 075 | 22 | | PA | | 6-0 | 31-31-11 | D04725P | | 1 | | TB0145Z | 132 | BJ | | ALL |
| 076 | 22 | | PA | | 6-0 | 31-31-11 | D04725P | | 2 | | TB0145Y | A134 | BJ | | ALL |
| 078 | 24 | | PK | | 7-0 | 31-31-11 | D04741P | | 4 | | D04725P | 5 | | | ALL |
| 079 | 24 | | PV | DD | 4-0 | 31-31-17 | TB0145X | B142 | BJ | | D00327D | B01 | | | ALL |
| 079Z | | | | DD | 0-0 | 31-31-17 | TB0145X | DED | | | D00327D | DED | | | ALL |
| 07A | 20 | | PA | | 5-0 | 31-31-15 | D04731P | | 17 | | GDX0004 | A.. | 2 | | 157, 167-199, 277-299 |
| 080 | 24 | | PV | DE | 5-0 | 31-31-17 | TB0145X | A108 | BJ | | D00327A | A01 | | | 050-099, 150-199, 275-276 |
| 080 | 24 | | PV | DE | 5-0 | 31-31-17 | TB0145X | A114 | BJ | | D00327A | A01 | | | 277-299 |
| 080Z | | | | DE | 0-0 | 31-31-17 | TB0145X | DED | | | D00327A | DED | | | ALL |
| 081 | 24 | | PV | DF | 4-0 | 31-31-17 | TB0145X | D142 | BJ | | D00327A | B01 | | | ALL |
| 081Z | | | | DF | 0-0 | 31-31-17 | TB0145X | DED | | | D00327A | DED | | | ALL |
| 082 | 24 | | PV | DG | 5-0 | 31-31-17 | TB0145R | C187 | 2 | | D00327A | C01 | | | 050-099, 150-154, 162-163, 275-276 |
| 082 | 24 | | PV | DG | 4-0 | 31-31-17 | TB0145R | C187 | 2 | | D00327A | C01 | | | 155-157, 164-199, 277-299 |
| 082Z | | | | DG | 0-0 | 31-31-17 | TB0145R | DED | | | D00327A | DED | | | ALL |
| 083 | 24 | | PV | DH | 4-0 | 31-31-17 | TB0145R | C188 | 2 | | D00327D | D01 | | | ALL |
| 083Z | | | | DH | 0-0 | 31-31-17 | TB0145R | DED | | | D00327D | DED | | | ALL |
| 084 | 24 | | PK | | 4-0 | 31-31-13 | D05229P | | 1 | | D00327A | E01 | | | ALL |
| 085 | 24 | | PK | | 3-0 | 31-31-13 | D00327A | F01 | | | D05733P | 14 | | | ALL |
| 086 | 24 | | PK | | 4-0 | 31-31-13 | D05229P | | 3 | | D00327D | J01 | | | ALL |
| 087 | 24 | | PK | | 4-0 | 31-31-13 | D05229P | | 4 | | D00327D | K01 | | | ALL |
| 088 | 24 | | PK | | 4-0 | 31-31-13 | D05229P | | 5 | | D00327D | C01 | | | ALL |
| 089 | 24 | | PK | | 4-0 | 31-31-13 | D05229P | | 6 | | D00327D | C03 | | | ALL |
| 090 | 24 | | PK | | 4-0 | 31-31-13 | D05229P | | 7 | | D00327A | H01 | | | ALL |
| 091 | 24 | | PK | | 4-0 | 31-31-13 | D05229P | | 8 | | D00327A | J01 | | | ALL |
| 092 | 24 | | PK | | 4-0 | 31-31-13 | D05229P | | 9 | | D00327A | B03 | | | ALL |
| 097 | 24 | | PV | DV | 4-0 | 31-31-11 | TB0145Y | C140 | BJ | | D00327A | H03 | | | ALL |
| 097Z | | | | DV | 0-0 | 31-31-11 | TB0145Y | DED | | | D00327A | DED | | | ALL |
| 098 | 22 | | PA | | 3-0 | 31-31-13 | GDX0007 | A.. | 2 | | D00327B | C02 | | | ALL |
| 099 | 22 | | PA | | 5-0 | 31-31-11 | D04741P | | 1 | | TB0145Z | 131 | BJ | | ALL |
| 09A | 20 | | PA | | 5-0 | 31-31-15 | D04731P | | 18 | | GDX0004 | A.. | 2 | | 157, 167-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 48

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | | |
| 100 | 22 | | PA | | 4-0 | 31-31-11 | D04711P | | 23 | | | | TB0145Z | 132 | BJ | | ALL |
| 101 | 22 | | PA | | 4-0 | 31-31-11 | D04711P | | 24 | | | | TB0145Y | A134 | BJ | | ALL |
| 102 | 22 | | PA | | 5-0 | 31-31-11 | D04741P | | 2 | | | | TB0145Y | A134 | BJ | | ALL |
| 106 | 22 | | PA | | 3-8 | 34-46-12 | D05207P | | 15 | | | | D05227P | 13 | | | ALL |
| 107 | 24 | | PK | | 4-0 | 31-31-12 | TB0145Y | | C139 | BJ | | | D05703P | 52 | | | ALL |
| 108 | 24 | | PK | | 4-0 | 31-31-12 | D00327A | | G01 | | | | TB0145Y | C139 | BJ | | ALL |
| 116 | 22 | | PA | | 6-0 | 31-31-15 | D04731P | | 10 | | | | TB0145Z | 138 | BJ | | ALL |
| 120 | 24 | | PK | | 3-8 | 22-14-31 | D05227P | | 1 | | | | D05207P | 30 | | | ALL |
| 121 | 24 | | PK | | 3-8 | 22-14-31 | D05227P | | 2 | | | | D05207P | 7 | | | ALL |
| 122 | 24 | | PK | | 7-0 | 31-31-11 | D05227P | | 3 | | | | D04725P | 25 | | | ALL |
| 123 | 24 | | PK | | 5-0 | 31-51-41 | D05227P | | 4 | | | | D05733P | 21 | | | ALL |
| 124 | 24 | | PK | | 5-0 | 31-51-41 | D05227P | | 5 | | | | D05733P | 22 | | | ALL |
| 125 | 24 | | PK | | 5-0 | 31-51-41 | D05227P | | 6 | | | | D05733P | 23 | | | ALL |
| 126 | 24 | | PK | | 5-0 | 31-51-41 | D05227P | | 7 | | | | D05733P | 24 | | | ALL |
| 127 | 24 | | PK | | 5-0 | 31-51-42 | D05227P | | 11 | | | | D05733P | 20 | | | ALL |
| 128 | 24 | | PK | | 5-0 | 34-16-11 | D05227P | | 12 | | | | D05733P | 18 | | | ALL |
| 129 | 24 | | PK | | 5-0 | 31-51-43 | D05227P | | 32 | | | | D05733P | 19 | | | ALL |
| 130 | 24 | | PK | | 6-0 | 34-53-11 | D05733P | | 36 | | | | D05227P | 29 | | | ALL |
| 131 | 24 | | PK | | 5-0 | 31-31-13 | D05227P | | 16 | | | | D00327A | J03 | | | ALL |
| 132 | 24 | | PK | | 5-0 | 34-61-15 | D05227P | | 23 | | | | D05733P | 28 | | | ALL |
| 133 | 24 | | PK | | 5-0 | 31-41-16 | D05227P | | 24 | | | | D05733P | 35 | | | ALL |
| 134 | 24 | | PK | | 5-0 | 31-51-41 | D05227P | | 28 | | | | D05733P | 37 | | | ALL |
| 135 | 24 | | PK | | 4-0 | 31-31-21 | TB0145X | | B002 | BJ | | | TB0145R | C026 | 2 | * | 050-099, 150-199, 275-276 |
| 135 | 24 | | PK | | 3-0 | 31-31-21 | TB0145X | | B008 | BJ | | | TB0145R | C103 | 2 | * | 277-299 |
| 136 | 24 | | PK | | 5-0 | 31-31-22 | D04725P | | 49 | | | | D00327D | A05 | | | ALL |
| 138 | 24 | | PK | | 4-0 | 31-31-22 | TB0145X | | C163 | BJ | | | D00327A | D03 | | | ALL |
| 139 | 24 | | PK | | 4-0 | 31-31-22 | TB0145X | | D163 | BJ | | | D00327D | F03 | | | ALL |
| 140 | 24 | | PK | | 5-0 | 31-41-16 | D05227P | | 30 | | | | D05733P | 41 | | | ALL |
| 149 | 24 | | PK | | 4-0 | 31-31-18 | TB0145X | | A149 | BJ | | | D00327A | D05 | | | ALL |
| 150 | 24 | | PK | | 4-0 | 31-31-18 | TB0145X | | B149 | BJ | | | D00327A | E05 | | | ALL |
| 151 | 24 | | PK | | 4-0 | 31-31-18 | TB0145X | | C149 | BJ | | | D00327A | F05 | | | ALL |
| 152 | 24 | | PK | | 4-0 | 31-31-18 | TB0145X | | D149 | BJ | | | D00327A | C05 | | | ALL |
| 153 | 24 | | PK | | 4-0 | 31-31-18 | TB0145X | | A151 | BJ | | | D00327D | D05 | | | ALL |
| 154 | 24 | | PK | | 4-0 | 31-31-18 | TB0145X | | B151 | BJ | | | D00327D | E05 | | | ALL |
| 155 | 24 | | PK | | 4-0 | 31-31-18 | TB0145X | | C151 | BJ | | | D00327D | F05 | | | ALL |
| 156 | 24 | | PK | | 5-0 | 31-31-18 | TB0145X | | D151 | BJ | | | D00327D | G05 | | | ALL |
| 160 | 24 | | PK | | 5-0 | 31-31-14 | D05207P | | 10 | | | | D00327A | K01 | | | ALL |
| 163 | 24 | | PK | | 4-0 | 31-31-14 | D00327D | | A03 | | | | TB0145X | D141 | BJ | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 49
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | |
| 165 | 24 | | PK | 4-0 | 34-61-27 | TB0145D | A197 | 2 | | D06199P | 1 | | | 157, 167-199, 277-299 | | |
| 169 | 24 | | PK | 5-0 | 31-31-15 | D05207P | | 11 | | D00327A | F07 | | | ALL | | |
| 173 | 24 | | PK | 5-0 | 31-31-19 | D00327A | | E03 | | D05207P | 17 | | | ALL | | |
| 174 | 24 | | PK | 4-0 | SPARE | D00327A | | E12 | | D05229P | 33 | | | ALL | | |
| 176 | 24 | | PK | 4-0 | 31-31-19 | D00327A | | H12 | | TB0145Y | A148 | BJ | | ALL | | |
| 177 | 22 | | PA | 4-0 | 31-31-22 | TB0145Z | | 165 | BJ | D00327B | A15 | | | ALL | | |
| 179 | 22 | | PA | 4-0 | 31-31-22 | TB0145Z | | 166 | BJ | D00327E | A12 | | | ALL | | |
| 180 | 22 | | PA | 5-0 | 31-31-22 | D05229P | | 34 | | TB0145Z | 166 | BJ | | ALL | | |
| 181 | 22 | | PA | 4-0 | 31-31-22 | TB0145Z | | 166 | BJ | D00327B | A12 | | | ALL | | |
| 182 | 24 | | PK | 5-0 | 31-31-22 | D04725P | | 55 | | D00327A | B05 | | | ALL | | |
| 183 | 24 | | PK | 4-0 | 31-31-22 | D05229P | | 10 | | D00327A | J07 | | | ALL | | |
| 184 | 24 | | PK | 4-0 | 31-31-22 | TB0145X | | A038 | BJ | D00327D | C05 | | | ALL | | |
| 185 | 24 | | PK | 4-0 | 31-31-22 | D05703P | | 30 | | D00327A | A03 | | | ALL | | |
| 187 | 24 | | PK | 5-0 | 31-31-22 | TB0145X | | C142 | BJ | D00327D | B07 | | | ALL | | |
| 188 | 22 | | PA | 4-0 | 31-31-22 | TB0145Z | | 166 | BJ | TB0145Z | 153 | BJ | | ALL | | |
| 189 | 22 | | PA | 4-0 | 31-36-11 | D04215P | | 6 | | D04765P | 23 | | | ALL | | |
| 191 | 22 | | PA | 4-0 | 31-31-14 | D00327D | | K03 | | D05207P | 31 | | | ALL | | |
| 192 | 22 | | PQ | HQ | 5-0 | 31-31-14 | D00327A | K03 | | TB0145X | A107 | BJ | | 050-099, 150-199, 275-276 | | |
| 192 | 22 | | PQ | HQ | 5-0 | 31-31-14 | D00327A | K03 | | TB0145X | A113 | BJ | | 277-299 | | |
| 192Z | | | | HQ | 0-0 | 31-31-14 | D00327A | DED | | TB0145X | DED | | | ALL | | |
| 195 | 22 | | PA | | 6-0 | 34-22-38 | D05227P | 31 | | TB0145Y | A044 | BJ | | ALL | | |
| 202B | 22 | | PB | IB | 4-0 | 34-12-21 | D05703P | 54 | | GDY0007 | A.. | 2 | | ALL | | |
| 202R | 22 | | PB | IB | 0-0 | 34-12-21 | D05703P | 55 | | TB0145Z | 35 | BJ | | ALL | | |
| 203 | 20 | | UA | | 1-6 | 34-61-23 | GDY0011 | S.. | 2 | TB0145X | REF | | IC | 050-099, 150-157, 275-276 | | |
| 203 | 20 | | UA | | 1-6 | 34-61-23 | GDX0009 | S.. | 2 | TB0145X | REF | | IC | 162-199 | | |
| 203B | 24 | | PW | IC | 4-0 | 34-61-23 | D05703P | 13 | | TB0145X | B157 | BJ | | ALL | | |
| 203R | 24 | | PW | IC | 0-0 | 34-61-23 | D05703P | 12 | | TB0145X | A157 | BJ | | ALL | | |
| 203Z | | | | IC | 0-0 | 34-61-23 | D05703P | 14 | | TB0145X | REF | | IC | 050-099, 150-199, 275-276 | | |
| 203Z | | | | IC | 0-0 | 34-61-23 | D05703P | 14 | | GDY0009 | S.. | 2 | | 277-299 | | |
| 204 | 20 | | UA | | 1-6 | 34-61-23 | GDY0011 | S.. | 2 | TB0145X | REF | | ID | 050-099, 150-157, 275-276 | | |
| 204 | 20 | | UA | | 1-6 | 34-61-23 | GDX0009 | S.. | 2 | TB0145X | REF | | ID | 162-199 | | |
| 204B | 24 | | PW | ID | 4-0 | 34-61-23 | D05703P | 16 | | TB0145X | D157 | BJ | | ALL | | |
| 204R | 24 | | PW | ID | 0-0 | 34-61-23 | D05703P | 15 | | TB0145X | C157 | BJ | | ALL | | |
| 204Z | | | | ID | 0-0 | 34-61-23 | D05703P | 17 | | TB0145X | REF | | ID | 050-099, 150-199, 275-276 | | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 50

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | |
| 219B | 24 | PW | IS | 6-0 | 31-31-11 | D04725P | | 36 | | | | TB0145Y | C129 | BJ | | ALL |
| 219R | 24 | PW | IS | 0-0 | 31-31-11 | D04725P | | 35 | | | | TB0145Y | A129 | BJ | | ALL |
| 219Z | | | IS | 0-0 | 31-31-11 | D04725P | | 7 | | | | GDY0006 | S.. | 2 | | ALL |
| 220 | 20 | UA | | 2-0 | 31-31-11 | D00327A | | REF | | IT | | GDY0008 | S.. | 2 | | ALL |
| 220B | 24 | PW | IT | 5-0 | 31-31-11 | D04725P | | 11 | | | | D00327A | H11 | | | ALL |
| 220R | 24 | PW | IT | 0-0 | 31-31-11 | D04725P | | 10 | | | | D00327A | G11 | | | ALL |
| 220Z | | | IT | 0-0 | 31-31-11 | D04725P | | 26 | | | | D00327A | REF | | IT | ALL |
| 221 | 20 | UA | | 2-0 | 31-31-11 | D00327A | | REF | | IU | | GDY0008 | S.. | 2 | | ALL |
| 221B | 24 | PW | IU | 5-0 | 31-31-11 | D04725P | | 15 | | | | D00327A | K09 | | | ALL |
| 221R | 24 | PW | IU | 0-0 | 31-31-11 | D04725P | | 14 | | | | D00327A | J09 | | | ALL |
| 221Z | | | IU | 0-0 | 31-31-11 | D04725P | | 29 | | | | D00327A | REF | | IU | ALL |
| 222 | 20 | UA | | 2-0 | 31-31-11 | D00327A | | REF | | IV | | GDY0007 | S.. | 2 | | ALL |
| 222B | 24 | PW | IV | 5-0 | 31-31-11 | D04725P | | 17 | | | | D00327A | H09 | | | ALL |
| 222R | 24 | PW | IV | 0-0 | 31-31-11 | D04725P | | 16 | | | | D00327A | G09 | | | ALL |
| 222Z | | | IV | 0-0 | 31-31-11 | D04725P | | 30 | | | | D00327A | REF | | IV | ALL |
| 223B | 24 | PW | IW | 4-0 | 31-31-11 | D00327A | | B09 | | | | TB0145Y | C129 | BJ | | ALL |
| 223R | 24 | PW | IW | 0-0 | 31-31-11 | D00327A | | A09 | | | | TB0145Y | A129 | BJ | | ALL |
| 223Z | | | IW | 0-0 | 31-31-11 | D00327A | | DED | | | | GDY0006 | S.. | 2 | | ALL |
| 224 | 20 | UA | | 2-0 | 31-31-11 | D00327A | | REF | | IX | | GDY0007 | S.. | 2 | | ALL |
| 224B | 24 | PW | IX | 4-0 | 31-31-11 | D04741P | | 11 | | | | D00327A | K11 | | | ALL |
| 224R | 24 | PW | IX | 0-0 | 31-31-11 | D04741P | | 10 | | | | D00327A | J11 | | | ALL |
| 224Z | | | IX | 0-0 | 31-31-11 | D04741P | | 21 | | | | D00327A | REF | | IX | ALL |
| 225 | 20 | UA | | 2-0 | 31-31-14 | D00327A | | REF | | IY | | GDY0007 | S.. | 2 | | ALL |
| 225B | 24 | PW | IY | 4-0 | 31-31-14 | D05703P | | 36 | | | | D00327A | F14 | | | ALL |
| 225R | 24 | PW | IY | 0-0 | 31-31-14 | D05703P | | 35 | | | | D00327A | E14 | | | ALL |
| 225Z | | | IY | 0-0 | 31-31-14 | D05703P | | 37 | | | | D00327A | REF | | IY | ALL |
| 226 | 20 | UA | | 2-0 | 31-31-14 | TB0145X | | REF | | JA | | GDY0006 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 226B | 24 | PW | JA | 4-0 | 31-31-14 | D00327D | | B13 | | | | TB0145X | A142 | BJ | | ALL |
| 226R | 24 | PW | JA | 0-0 | 31-31-14 | D00327D | | A13 | | | | TB0145X | A141 | BJ | | ALL |
| 226Z | | | JA | 0-0 | 31-31-14 | D00327D | | DED | | | | TB0145X | REF | | JA | 050-099, 152-199, 275-299 |
| 226Z | | | JA | 0-0 | 31-31-14 | D00327D | | DED | | | | GDY0008 | S.. | 2 | | 150-151 |
| 227 | 20 | UA | | 2-0 | 31-31-14 | D00327A | | REF | | JB | | GDY0008 | S.. | 2 | | ALL |
| 227B | 24 | PW | JB | 4-0 | 31-31-14 | D05207P | | 2 | | | | D00327A | B13 | | | ALL |
| 227R | 24 | PW | JB | 0-0 | 31-31-14 | D05207P | | 1 | | | | D00327A | A13 | | | ALL |
| 227Z | | | JB | 0-0 | 31-31-14 | D05207P | | 3 | | | | D00327A | REF | | JB | ALL |
| 228B | 24 | PW | JC | 4-0 | 31-31-12 | TB0145X | | D145 | BJ | | | D00327A | F13 | | | ALL |
| 228R | 24 | PW | JC | 0-0 | 31-31-12 | TB0145X | | C145 | BJ | | | D00327A | E13 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 52

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | | |
| 228Z | | | | JC | 0-0 | 31-31-12 | GDY0009 | S.. | 2 | | | | D00327A | DED | | | 050-099, 150-199, 275-276 |
| 228Z | | | | JC | 0-0 | 31-31-12 | GDY0008 | S.. | 2 | | | | D00327A | DED | | | 277-299 |
| 229 | 20 | | UA | | 2-0 | 31-25-11 | D00327A | REF | | | JD | | GDX0008 | S.. | 2 | | ALL |
| 229B | 24 | | PW | JD | 4-0 | 31-25-11 | D05703P | | 32 | | | | D00327A | H13 | | | ALL |
| 229R | 24 | | PW | JD | 0-0 | 31-25-11 | D05703P | | 31 | | | | D00327A | G13 | | | ALL |
| 229Z | | | | JD | 0-0 | 31-25-11 | D05703P | | 33 | | | | D00327A | REF | | JD | ALL |
| 230 | 20 | | UA | | 2-0 | 31-31-12 | TB0145Y | REF | | | JE | | GDX0007 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 230B | 24 | | PW | JE | 4-0 | 31-31-12 | TB0145Y | C143 | | BJ | | | D00327A | B14 | | | ALL |
| 230R | 24 | | PW | JE | 0-0 | 31-31-12 | TB0145Y | A143 | | BJ | | | D00327A | A14 | | | ALL |
| 230Z | | | | JE | 0-0 | 31-31-12 | TB0145Y | REF | | | JE | | D00327A | DED | | | 050-099, 152-199, 275-299 |
| 230Z | | | | JE | 0-0 | 31-31-12 | GDY0008 | S.. | 2 | | | | D00327A | DED | | | 150-151 |
| 237B | 24 | | PL | JL | 4-0 | 31-31-13 | D04711P | | 16 | | | | D00327B | B12 | | | ALL |
| 237R | 24 | | PL | JL | 0-0 | 31-31-13 | D04711P | | 15 | | | | D00327B | B10 | | | ALL |
| 238B | 24 | | PL | JM | 4-0 | 31-31-13 | D04711P | | 20 | | | | D00327E | B09 | | | ALL |
| 238R | 24 | | PL | JM | 0-0 | 31-31-13 | D04711P | | 19 | | | | D00327E | B07 | | | ALL |
| 240 | 20 | | UA | | 2-0 | 31-31-13 | D00327B | REF | | | JO | | GDX0007 | S.. | 2 | | ALL |
| 240B | 24 | | PW | JO | 5-0 | 31-31-13 | D04729P | | 5 | | | | D00327B | A02 | | | ALL |
| 240R | 24 | | PW | JO | 0-0 | 31-31-13 | D04729P | | 4 | | | | D00327B | A01 | | | ALL |
| 240Z | | | | JO | 0-0 | 31-31-13 | D04729P | | | | FB | | D00327B | REF | | JO | ALL |
| 241 | 20 | | UA | | 2-0 | 31-31-13 | D00327B | REF | | | JP | | GDX0007 | S.. | 2 | | ALL |
| 241B | 24 | | PW | JP | 5-0 | 31-31-13 | D04729P | | 9 | | | | D00327B | B05 | | | ALL |
| 241R | 24 | | PW | JP | 0-0 | 31-31-13 | D04729P | | 8 | | | | D00327B | B04 | | | ALL |
| 241Z | | | | JP | 0-0 | 31-31-13 | D04729P | | | | FB | | D00327B | REF | | JP | ALL |
| 242 | 20 | | UA | | 2-0 | 31-31-13 | D00327B | REF | | | JQ | | GDX0007 | S.. | 2 | | ALL |
| 242B | 24 | | PW | JQ | 5-0 | 31-31-13 | D04729P | | 7 | | | | D00327B | A05 | | | ALL |
| 242R | 24 | | PW | JQ | 0-0 | 31-31-13 | D04729P | | 6 | | | | D00327B | A04 | | | ALL |
| 242Z | | | | JQ | 0-0 | 31-31-13 | D04729P | | | | FB | | D00327B | REF | | JQ | ALL |
| 243B | 24 | | PL | JR | 5-0 | 31-31-13 | D04729P | | 2 | | | | D00327B | F15 | | | ALL |
| 243R | 24 | | PL | JR | 0-0 | 31-31-13 | D04729P | | 1 | | | | D00327B | F14 | | | ALL |
| 251 | 20 | | UA | | 2-0 | 34-61-14 | GDX0001 | S.. | 2 | | | | D05705J | | | KA | ALL |
| 251B | 24 | | PW | KA | 3-0 | 34-61-14 | D05703P | | 47 | | | | D05705J | 17 | | | ALL |
| 251R | 24 | | PW | KA | 0-0 | 34-61-14 | D05703P | | 46 | | | | D05705J | 16 | | | ALL |
| 251Z | | | | KA | 0-0 | 34-61-14 | D05703P | | 48 | | | | D05705J | | | KA | ALL |
| 252B | 24 | | PL | KB | 4-0 | 31-31-13 | D05207P | | 9 | | | | D00327B | C03 | | | ALL |
| 252R | 24 | | PL | KB | 0-0 | 31-31-13 | D05207P | | 8 | | | | D00327B | C01 | | | ALL |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | |
| 253B | 24 | PW | KC | 5-0 | 31-35-15 | TB0145X | B089 | BJ | | D05703P | 39 | | | 050-099, 150-199, 275-276 | | |
| 253B | 24 | PW | KC | 7-0 | 31-35-15 | D04667P | 34 | | | D05703P | 39 | | | 277 | | |
| 253B | 24 | PW | KC | 7-0 | 31-35-15 | TB0145X | C038 | BJ | | D05703P | 39 | | | 278-299 | | |
| 253R | 24 | PW | KC | 0-0 | 31-35-15 | TB0145X | A089 | BJ | | D05703P | 40 | | | 050-099, 150-199, 275-276 | | |
| 253R | 24 | PW | KC | 0-0 | 31-35-15 | D04667P | 33 | | | D05703P | 40 | | | 277 | | |
| 253R | 24 | PW | KC | 0-0 | 31-35-15 | TB0145X | D038 | BJ | | D05703P | 40 | | | 278-299 | | |
| 253Z | | | KC | 0-0 | 31-35-15 | GDY0013 | S.. | 2 | | D05703P | 41 | | | 050-099, 150-199, 275-276 | | |
| 253Z | | | KC | 0-0 | 31-35-15 | D04667P | 35 | | | D05703P | 41 | | | 277 | | |
| 253Z | | | KC | 0-0 | 31-35-15 | GDY0006 | S.. | 2 | | D05703P | 41 | | | 278-299 | | |
| 257B | 24 | PW | KG | 3-0 | 27-51-51 | D05207P | 13 | | | D05705J | 4 | | | ALL | | |
| 257R | 24 | PW | KG | 0-0 | 27-51-51 | D05207P | 12 | | | D05705J | 3 | | | ALL | | |
| 257Z | | | KG | 0-0 | 27-51-51 | D05207P | 14 | | | D05705J | 5 | | | ALL | | |
| 275 | 20 | UA | | 2-0 | 31-31-13 | TB0145Y | REF | | KY | GDY0007 | S.. | 2 | | 050-099, 152-199, 275-276 | | |
| 275B | 24 | PW | KY | 4-0 | 31-31-13 | D00327D | D14 | | | TB0145Y | C144 | BJ | | ALL | | |
| 275R | 24 | PW | KY | 0-0 | 31-31-13 | D00327D | C14 | | | TB0145Y | A144 | BJ | | ALL | | |
| 275Z | | | KY | 0-0 | 31-31-13 | D00327D | DED | | | TB0145Y | REF | | KY | 050-099, 152-199, 275-276 | | |
| 275Z | | | KY | 0-0 | 31-31-13 | D00327D | DED | | | GDY0008 | S.. | 2 | | 150-151, 277-299 | | |
| 276 | 20 | UA | | 2-0 | 34-61-14 | D05733P | REF | | LA | GDY0008 | S.. | 2 | | 050-099, 150-156, 162-166 | | |
| 276 | 20 | UA | | 2-0 | 34-61-14 | TB0145Y | REF | | LA | GDY0010 | S.. | 2 | | 157, 167-199, 275-276 | | |
| 276 | 20 | UA | | 2-0 | 34-61-14 | TB0145Y | REF | | LA | GDY0002 | S.. | 2 | | 277-299 | | |
| 276B | 24 | PW | LA | 5-0 | 34-61-14 | D05733P | 30 | | | D05227P | 18 | | | 050-099, 150-156, 162-166 | | |
| 276B | 24 | PW | LA | 6-0 | 34-61-14 | TB0145Y | C077 | BJ | | D05227P | 18 | | | 157, 167-199 | | |
| 276B | 24 | PW | LA | 7-0 | 34-61-14 | TB0145Y | C077 | BJ | | D05227P | 18 | | | 275-276 | | |
| 276B | 24 | PW | LA | 5-0 | 34-61-14 | TB0145Y | C019 | BJ | | D05227P | 18 | | | 277-278 | | |
| 276B | 24 | PW | LA | 4-0 | 34-61-14 | TB0145Y | C019 | BJ | | D05227P | 18 | | | 280-299 | | |
| 276R | 24 | PW | LA | 0-0 | 34-61-14 | D05733P | 29 | | | D05227P | 17 | | | 050-099, 150-156, 162-166 | | |
| 276R | 24 | PW | LA | 0-0 | 34-61-14 | TB0145Y | A077 | BJ | | D05227P | 17 | | | 157, 167-199, 275-276 | | |
| 276R | 24 | PW | LA | 0-0 | 34-61-14 | TB0145Y | A019 | BJ | | D05227P | 17 | | | 277-299 | | |
| 276Z | | | LA | 0-0 | 34-61-14 | D05733P | REF | | LA | D05227P | 19 | | | 050-099, 150-156, 162-166 | | |
| 276Z | | | LA | 0-0 | 34-61-14 | TB0145Y | REF | | LA | D05227P | 19 | | | 157, 167-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 54

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | |
| 277B | 24 | PW | LB | | 5-0 | 34-61-15 | D05733P | | 2 | | D05227P | 21 | | | ALL |
| 277R | 24 | PW | LB | | 0-0 | 34-61-15 | D05733P | | 1 | | D05227P | 20 | | | ALL |
| 277Z | | | LB | | 0-0 | 34-61-15 | D05733P | | 3 | | D05227P | 22 | | | ALL |
| 293B | 24 | PW | LR | | 5-0 | 31-31-14 | D00327D | | D13 | | TB0145Y | C003 | BJ | | 050-099, 150-199, 275-276 |
| 293B | 24 | PW | LR | | 5-0 | 31-31-14 | D00327D | | D13 | | TB0145Y | C009 | BJ | | 277-299 |
| 293R | 24 | PW | LR | | 0-0 | 31-31-14 | D00327D | | C13 | | TB0145Y | A003 | BJ | | 050-099, 150-199, 275-276 |
| 293R | 24 | PW | LR | | 0-0 | 31-31-14 | D00327D | | C13 | | TB0145Y | A009 | BJ | | 277-299 |
| 293Z | | | LR | | 0-0 | 31-31-14 | D00327D | | DED | | GDY0001 | S.. | 2 | | ALL |
| 296B | 24 | PW | LU | | 5-0 | 34-61-15 | TB0145Z | | 16 | BJ | D05733P | 43 | | | 050-099, 150-199, 275-276 |
| 296B | 24 | PW | LU | | 5-0 | 34-61-15 | TB0145Z | | 22 | BJ | D05733P | 43 | | | 277-299 |
| 296R | 24 | PW | LU | | 0-0 | 34-61-15 | TB0145Z | | 15 | BJ | D05733P | 42 | | | 050-099, 150-199, 275-276 |
| 296R | 24 | PW | LU | | 0-0 | 34-61-15 | TB0145Z | | 21 | BJ | D05733P | 42 | | | 277-299 |
| 296Z | | | LU | | 0-0 | 34-61-15 | GDY0003 | | S.. | 2 | D05733P | 44 | | | ALL |
| 299B | 24 | PW | LX | | 4-0 | 34-45-12 | D05207P | | 21 | | TB0145X | A119 | BJ | | 153-154 |
| 299R | 24 | PW | LX | | 0-0 | 34-45-12 | D05207P | | 20 | | TB0145X | A118 | BJ | | 153-154 |
| 299Z | | | LX | | 0-0 | 34-45-12 | D05207P | | 22 | | TB0145X | REF | | LX | 153-154 |
| 301B | 24 | PM | MA | | 3-0 | 34-12-21 | D05703P | | 50 | | TB0145X | B169 | BJ | | ALL |
| 301R | 24 | PM | MA | | 0-0 | 34-12-21 | D05703P | | 49 | | TB0145X | A169 | BJ | | ALL |
| 301Y | 24 | PM | MA | | 0-0 | 34-12-21 | D05703P | | 51 | | TB0145X | C169 | BJ | | ALL |
| 302 | 20 | UA | | | 2-0 | 31-31-19 | GDY0010 | | S.. | 2 | D00327B | REF | | MB | ALL |
| 302B | 24 | PX | MB | | 5-0 | 31-31-19 | TB0145R | | C021 | 2 | D00327B | C06 | | | 050-099, 150-199, 275-276 |
| 302B | 24 | PX | MB | | 5-0 | 31-31-19 | TB0145R | | C003 | 2 | D00327B | C06 | | | 277-299 |
| 302R | 24 | PX | MB | | 0-0 | 31-31-19 | TB0145Y | | A019 | BJ | D00327B | C05 | | | 050-099, 150-199, 275-276 |
| 302R | 24 | PX | MB | | 0-0 | 31-31-19 | TB0145G | | 2 | 2 | D00327B | C05 | | | 277-299 |
| 302Y | 24 | PX | MB | | 0-0 | 31-31-19 | TB0145R | | C022 | 2 | D00327B | C04 | | | 050-099, 150-199, 275-276 |
| 302Y | 24 | PX | MB | | 0-0 | 31-31-19 | TB0145R | | C001 | 2 | D00327B | C04 | | | 277-299 |
| 302Z | | | MB | | 0-0 | 31-31-19 | TB0145R | | DED | | D00327B | REF | | MB | ALL |
| 305B | 24 | PX | ME | | 7-0 | 31-31-19 | TB0145R | | A021 | 2 | D04725P | 38 | | | 050-099, 150-199, 275-276 |
| 305B | 24 | PX | ME | | 7-0 | 31-31-19 | TB0145R | | A003 | 2 | D04725P | 38 | | | 277-299 |
| 305R | 24 | PX | ME | | 0-0 | 31-31-19 | TB0145Y | | A019 | BJ | D04725P | 37 | | | 050-099, 150-199, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 55

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | |
| 305R | 24 | PX | ME | 0-0 | 31-31-19 | TB0145G | 2 | 2 | | D04725P | 37 | | | 277-299 | | |
| 305Y | 24 | PX | ME | 0-0 | 31-31-19 | TB0145R | A022 | 2 | | D04725P | 39 | | | 050-099, 150-199, 275-276 | | |
| 305Y | 24 | PX | ME | 0-0 | 31-31-19 | TB0145R | A001 | 2 | | D04725P | 39 | | | 277-299 | | |
| 305Z | | | ME | 0-0 | 31-31-19 | TB0145R | DED | | | D04725P | 40 | | | ALL | | |
| 509B | 24 | PL | UI | 5-0 | 31-31-15 | D04731P | 5 | | | D00327B | F07 | | | ALL | | |
| 509R | 24 | PL | UI | 0-0 | 31-31-15 | D04731P | 4 | | | D00327B | F05 | | | ALL | | |
| 510B | 24 | PW | UJ | 4-0 | 31-51-33 | D05733P | 39 | | | TB0145Z | 40 | BJ | | ALL | | |
| 510R | 24 | PW | UJ | 0-0 | 31-51-33 | D05733P | 38 | | | TB0145Z | 39 | BJ | | ALL | | |
| 510Z | | | UJ | 0-0 | 31-51-33 | D05733P | 40 | | | GDY0007 | S.. | 2 | | ALL | | |
| 512B | 24 | PL | UL | 5-0 | 31-31-15 | D04731P | 7 | | | D00327B | A09 | | | ALL | | |
| 512R | 24 | PL | UL | 0-0 | 31-31-15 | D04731P | 6 | | | D00327B | A07 | | | ALL | | |
| 513B | 24 | PL | UM | 5-0 | 31-31-15 | D04731P | 9 | | | D00327E | A09 | | | ALL | | |
| 513R | 24 | PL | UM | 0-0 | 31-31-15 | D04731P | 8 | | | D00327E | A07 | | | ALL | | |
| 514B | 24 | PW | UN | 5-0 | 31-31-14 | D00327D | B14 | | | TB0145Y | C004 | BJ | | 050-099, 150-199, 275-276 | | |
| 514B | 24 | PW | UN | 5-0 | 31-31-14 | D00327D | B14 | | | TB0145Y | C010 | BJ | | 277-299 | | |
| 514R | 24 | PW | UN | 0-0 | 31-31-14 | D00327D | A14 | | | TB0145Y | A004 | BJ | | 050-099, 150-199, 275-276 | | |
| 514R | 24 | PW | UN | 0-0 | 31-31-14 | D00327D | A14 | | | TB0145Y | A010 | BJ | | 277-299 | | |
| 514Z | | | UN | 0-0 | 31-31-14 | D00327D | DED | | | GDY0001 | S.. | 2 | | ALL | | |
| 518 | 20 | UA | | 2-0 | 34-46-11 | D00327D | REF | | FA | GDY0008 | S.. | 2 | | ALL | | |
| 518B | 24 | PW | UR | 3-0 | 34-46-11 | D05733P | 33 | | | D00327D | K13 | | | ALL | | |
| 518R | 24 | PW | UR | 0-0 | 34-46-11 | D05733P | 32 | | | D00327D | J13 | | | ALL | | |
| 518Z | | | UR | 0-0 | 34-46-11 | D05733P | 34 | | | D00327D | REF | | FA | ALL | | |
| 519 | 20 | UA | | 2-0 | 31-31-19 | GDY0006 | S.. | 2 | | D00327E | REF | | US | ALL | | |
| 519B | 24 | PW | US | 4-0 | 31-31-19 | D05705J | 10 | | | D00327E | B05 | | | ALL | | |
| 519R | 24 | PW | US | 0-0 | 31-31-19 | D05705J | 9 | | | D00327E | B04 | | | ALL | | |
| 519Z | | | US | 0-0 | 31-31-19 | D05705J | 11 | | | D00327E | REF | | US | ALL | | |
| 523 | 20 | UA | | 2-0 | 31-31-20 | D00327A | REF | | UW | GDY0009 | S.. | 2 | | ALL | | |
| 523B | 24 | PW | UW | 3-0 | 31-31-20 | D00327A | D13 | | | D05753P | 17 | | | ALL | | |
| 523R | 24 | PW | UW | 0-0 | 31-31-20 | D00327A | C13 | | | D05753P | 16 | | | ALL | | |
| 523Z | | | UW | 0-0 | 31-31-20 | D00327A | REF | | UW | D05753P | 18 | | | ALL | | |
| 525 | 20 | UA | | 2-0 | 31-31-20 | GDY0013 | S.. | 2 | | TB0145Y | REF | | UY | 150-156, 162-166 | | |
| 525 | 20 | UA | | 2-0 | 31-31-20 | GDY0011 | S.. | 2 | | TB0145Z | REF | | UY | 157, 167-199 | | |
| 525 | 20 | UA | | 2-0 | 31-31-20 | TB0145Z | REF | | UY | GDY0011 | S.. | 2 | | 275-276 | | |
| 525 | 20 | UA | | 4-0 | 31-31-20 | TB0145Z | REF | | UY | GDY0006 | S.. | 2 | | 277-278 | | |
| 525 | 20 | UA | | 3-0 | 31-31-20 | TB0145Y | REF | | UY | GDY0003 | S.. | 2 | | 280-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 56

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | |
| 525B | 24 | PW | UY | | 4-0 | 31-31-20 | D00327D | F13 | | | TB0145Y | C033 | BJ | | 050-099, 150-156, 162-166 |
| 525B | 24 | PW | UY | | 4-0 | 31-31-20 | D00327D | F13 | | | TB0145Z | 182 | BJ | | 157, 167-199 |
| 525B | 24 | PW | UY | | 6-0 | 31-31-20 | D00327D | F13 | | | TB0145Z | 184 | BJ | | 275-276 |
| 525B | 24 | PW | UY | | 4-0 | 31-31-20 | D00327D | F13 | | | TB0145Z | 126 | BJ | | 277-299 |
| 525R | 24 | PW | UY | | 0-0 | 31-31-20 | D00327D | E13 | | | TB0145Y | A033 | BJ | | 050-099, 150-156, 162-166 |
| 525R | 24 | PW | UY | | 0-0 | 31-31-20 | D00327D | E13 | | | TB0145Z | 181 | BJ | | 157, 167-199 |
| 525R | 24 | PW | UY | | 0-0 | 31-31-20 | D00327D | E13 | | | TB0145Z | 183 | BJ | | 275-276 |
| 525R | 24 | PW | UY | | 0-0 | 31-31-20 | D00327D | E13 | | | TB0145Z | 125 | BJ | | 277-299 |
| 525Z | | | UY | | 0-0 | 31-31-20 | D00327D | DED | | | GDY0007 | S.. | 2 | | 050-099 |
| 525Z | | | UY | | 0-0 | 31-31-20 | D00327D | DED | | | TB0145Y | REF | | UY | 150-156, 162-166 |
| 525Z | | | UY | | 0-0 | 31-31-20 | D00327D | DED | | | TB0145Z | REF | | UY | 157, 167-199, 275-276 |
| 525Z | | | UY | | 0-0 | 31-31-20 | TB0145Z | REF | | UY | D00327D | DED | | | 277-278 |
| 525Z | | | UY | | 0-0 | 31-31-20 | TB0145Y | REF | | UY | D00327D | DED | | | 280-299 |
| 535 | 20 | UA | | | 2-0 | 31-31-14 | D00327A | REF | | VJ | GDY0008 | S.. | 2 | | ALL |
| 535B | 24 | PW | VJ | | 3-0 | 31-31-14 | D00327A | K13 | | | D05753P | 14 | | | ALL |
| 535R | 24 | PW | VJ | | 0-0 | 31-31-14 | D00327A | J13 | | | D05753P | 13 | | | ALL |
| 535Z | | | VJ | | 0-0 | 31-31-14 | D00327A | REF | | VJ | D05753P | 15 | | | ALL |
| 537B | 24 | PW | VL | | 4-0 | 31-31-14 | D05207P | 5 | | | TB0145Y | C004 | BJ | | 050-099, 150-199, 275-276 |
| 537B | 24 | PW | VL | | 4-0 | 31-31-14 | D05207P | 5 | | | TB0145Y | C010 | BJ | | 277-299 |
| 537R | 24 | PW | VL | | 0-0 | 31-31-14 | D05207P | 4 | | | TB0145Y | A004 | BJ | | 050-099, 150-199, 275-276 |
| 537R | 24 | PW | VL | | 0-0 | 31-31-14 | D05207P | 4 | | | TB0145Y | A010 | BJ | | 277-299 |
| 537Z | | | VL | | 0-0 | 31-31-14 | D05207P | 6 | | | GDY0001 | S.. | 2 | | ALL |
| 538B | 24 | PW | VM | | 4-0 | 31-31-22 | TB0145Y | A050 | BJ | | D00327E | A14 | | | 050-099, 150-199, 275-276 |
| 538B | 24 | PW | VM | | 5-0 | 31-31-22 | TB0145Y | A086 | BJ | | D00327E | A14 | | | 277-278 |
| 538B | 24 | PW | VM | | 4-0 | 31-31-22 | TB0145Y | A086 | BJ | | D00327E | A14 | | | 280-299 |
| 538R | 24 | PW | VM | | 0-0 | 31-31-22 | TB0145X | C048 | BJ | | D00327E | A13 | | | 050-099, 150-199, 275-276 |
| 538R | 24 | PW | VM | | 0-0 | 31-31-22 | TB0145X | C084 | BJ | | D00327E | A13 | | | 277-299 |
| 538Z | | | VM | | 0-0 | 31-31-22 | GDY0009 | S.. | 2 | | D00327E | DED | | | 050-099, 150-199, 275-276 |
| 538Z | | | VM | | 0-0 | 31-31-22 | GDY0013 | S.. | 2 | | D00327E | DED | | | 277-299 |
| 546B | 24 | PW | VU | | 5-0 | 31-35-11 | D05703P | 26 | | | D04765P | 27 | | | ALL |
| 546R | 24 | PW | VU | | 0-0 | 31-35-11 | D05703P | 25 | | | D04765P | 28 | | | ALL |
| 546Z | | | VU | | 0-0 | 31-35-11 | D05703P | 27 | | | D04765P | 29 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 57
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | |
| 560 | 20 | UA | | | 2-0 | 31-35-11 | D00327E | | REF | | WJ | GDX0007 | S.. | 2 | | ALL |
| 560B | 24 | PW | WJ | | 4-0 | 31-35-11 | D00327E | | H06 | | | D05753P | 11 | | | ALL |
| 560R | 24 | PW | WJ | | 0-0 | 31-35-11 | D00327E | | H05 | | | D05753P | 10 | | | ALL |
| 560Z | | | WJ | | 0-0 | 31-35-11 | D00327E | | REF | | WJ | D05753P | 12 | | | ALL |
| 561B | 24 | PW | WK | | 5-0 | 31-35-11 | D04725P | | 52 | | | D05753P | 54 | | | ALL |
| 561R | 24 | PW | WK | | 0-0 | 31-35-11 | D04725P | | 51 | | | D05753P | 53 | | | ALL |
| 561Z | | | WK | | 0-0 | 31-35-11 | D04725P | | 50 | | | D05753P | 55 | | | ALL |
| 562B | 24 | PW | WL | | 5-0 | 31-31-20 | D05753P | | 20 | | | TB0145Y | C109 | BJ | | 050-099, 150-199, 275-276 |
| 562B | 24 | PW | WL | | 5-0 | 31-31-20 | D05753P | | 20 | | | TB0145Y | C115 | BJ | | 277-299 |
| 562R | 24 | PW | WL | | 0-0 | 31-31-20 | D05753P | | 19 | | | TB0145Y | A109 | BJ | | 050-099, 150-199, 275-276 |
| 562R | 24 | PW | WL | | 0-0 | 31-31-20 | D05753P | | 19 | | | TB0145Y | A115 | BJ | | 277-299 |
| 562Z | | | WL | | 0-0 | 31-31-20 | D05753P | | 21 | | | GDY0002 | S.. | 2 | | ALL |
| 563B | 24 | PW | WM | | 5-0 | 31-31-20 | D00327D | | K14 | | | TB0145Y | C109 | BJ | | 050-099, 150-199, 275-276 |
| 563B | 24 | PW | WM | | 5-0 | 31-31-20 | D00327D | | K14 | | | TB0145Y | C115 | BJ | | 277-299 |
| 563R | 24 | PW | WM | | 0-0 | 31-31-20 | D00327D | | J14 | | | TB0145Y | A109 | BJ | | 050-099, 150-199, 275-276 |
| 563Z | | | WM | | 0-0 | 31-31-20 | D00327D | | DED | | | GDY0002 | S.. | 2 | | ALL |
| 564 | 20 | UA | | | 2-0 | 31-31-20 | D00327D | | REF | | WN | GDX0009 | S.. | 2 | | ALL |
| 564B | 24 | PW | WN | | 3-0 | 31-31-20 | D05753P | | 3 | | | D00327D | H13 | | | ALL |
| 564R | 24 | PW | WN | | 0-0 | 31-31-20 | D05753P | | 2 | | | D00327D | G13 | | | ALL |
| 564Z | | | WN | | 0-0 | 31-31-20 | D05753P | | 1 | | | D00327D | REF | | WN | ALL |
| 565B | 24 | PW | WO | | 4-0 | 31-31-20 | TB0145X | | B145 | BJ | | D00327A | B15 | | | ALL |
| 565R | 24 | PW | WO | | 0-0 | 31-31-20 | TB0145X | | A145 | BJ | | D00327A | A15 | | | ALL |
| 565Z | | | WO | | 0-0 | 31-31-20 | GDY0009 | | S.. | 2 | | D00327A | DED | | | 050-099, 150-199, 275-276 |
| 565Z | | | WO | | 0-0 | 31-31-20 | GDY0008 | | S.. | 2 | | D00327A | DED | | | 277-299 |
| 566B | 24 | PW | WP | | 5-0 | 31-31-20 | D05229P | | 26 | | | TB0145Y | C111 | BJ | | 050-099, 150-199, 275-276 |
| 566B | 24 | PW | WP | | 5-0 | 31-31-20 | D05229P | | 26 | | | TB0145Y | C117 | BJ | | 277-299 |
| 566R | 24 | PW | WP | | 0-0 | 31-31-20 | D05229P | | 25 | | | TB0145Y | A111 | BJ | | 050-099, 150-199, 275-276 |
| 566R | 24 | PW | WP | | 0-0 | 31-31-20 | D05229P | | 25 | | | TB0145Y | A117 | BJ | | 277-299 |
| 566Z | | | WP | | 0-0 | 31-31-20 | D05229P | | 27 | | | GDY0002 | S.. | 2 | | ALL |
| 567B | 24 | PW | WQ | | 5-0 | 31-31-20 | D00327A | | K14 | | | TB0145Y | C111 | BJ | | 050-099, 150-199, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 58

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | |
| 567B | 24 | PW | WQ | 5-0 | 31-31-20 | D00327A | | K14 | | TB0145Y | C117 | BJ | | 277-299 | |
| 567R | 24 | PW | WQ | 0-0 | 31-31-20 | D00327A | | J14 | | TB0145Y | A111 | BJ | | 050-099, 150-199, 275-276 | |
| 567R | 24 | PW | WQ | 0-0 | 31-31-20 | D00327A | | J14 | | TB0145Y | A117 | BJ | | 277-299 | |
| 567Z | | | WQ | 0-0 | 31-31-20 | D00327A | | DED | | GDY0002 | S.. | 2 | | ALL | |
| 568B | 24 | PW | WR | 4-0 | 31-31-20 | D05227P | | 34 | | TB0145Y | C113 | BJ | | 050-099, 150-199, 275-276 | |
| 568B | 24 | PW | WR | 4-0 | 31-31-20 | D05227P | | 34 | | TB0145Y | C119 | BJ | | 277-299 | |
| 568R | 24 | PW | WR | 0-0 | 31-31-20 | D05227P | | 33 | | TB0145Y | A113 | BJ | | 050-099, 150-199, 275-276 | |
| 568R | 24 | PW | WR | 0-0 | 31-31-20 | D05227P | | 33 | | TB0145Y | A119 | BJ | | 277-299 | |
| 568Z | | | WR | 0-0 | 31-31-20 | D05227P | | 35 | | GDY0003 | S.. | 2 | | 050-099, 150-199, 275-276 | |
| 568Z | | | WR | 0-0 | 31-31-20 | D05227P | | 35 | | GDY0002 | S.. | 2 | | 277-299 | |
| 570B | 24 | PW | WT | 5-0 | 31-31-20 | D00327A | | D14 | | TB0145Y | C113 | BJ | | 050-099, 150-199, 275-276 | |
| 570B | 24 | PW | WT | 5-0 | 31-31-20 | D00327A | | D14 | | TB0145Y | C119 | BJ | | 277-299 | |
| 570R | 24 | PW | WT | 0-0 | 31-31-20 | D00327A | | C14 | | TB0145Y | A113 | BJ | | 050-099, 150-199, 275-276 | |
| 570R | 24 | PW | WT | 0-0 | 31-31-20 | D00327A | | C14 | | TB0145Y | A119 | BJ | | 277-299 | |
| 570Z | | | WT | 0-0 | 31-31-20 | D00327A | | DED | | GDY0003 | S.. | 2 | | 050-099, 150-199, 275-276 | |
| 571B | 24 | PW | WU | 4-0 | 31-31-20 | D05227P | | 37 | | GDY0002 | S.. | 2 | | 277-299 | |
| 571B | 24 | PW | WU | 4-0 | 31-31-20 | D05227P | | 37 | | TB0145Y | C114 | BJ | | 050-099, 150-199, 275-276 | |
| 571R | 24 | PW | WU | 0-0 | 31-31-20 | D05227P | | 36 | | TB0145Y | C120 | BJ | | 277-299 | |
| 571R | 24 | PW | WU | 0-0 | 31-31-20 | D05227P | | 36 | | TB0145Y | A114 | BJ | | 050-099, 150-199, 275-276 | |
| 571R | 24 | PW | WU | 0-0 | 31-31-20 | D05227P | | 36 | | TB0145Y | A120 | BJ | | 277-299 | |
| 571Z | | | WU | 0-0 | 31-31-20 | D05227P | | 38 | | GDY0003 | S.. | 2 | | ALL | |
| 572B | 24 | PW | WV | 5-0 | 31-31-20 | D00327D | | F14 | | TB0145Y | C114 | BJ | | 050-099, 150-199, 275-276 | |
| 572B | 24 | PW | WV | 5-0 | 31-31-20 | D00327D | | F14 | | TB0145Y | C120 | BJ | | 277-299 | |
| 572R | 24 | PW | WV | 0-0 | 31-31-20 | D00327D | | E14 | | TB0145Y | A114 | BJ | | 050-099, 150-199, 275-276 | |
| 572R | 24 | PW | WV | 0-0 | 31-31-20 | D00327D | | E14 | | TB0145Y | A120 | BJ | | 277-299 | |
| 572Z | | | WV | 0-0 | 31-31-20 | D00327D | | DED | | GDY0003 | S.. | 2 | | ALL | |
| 573B | 24 | PW | WV | 5-0 | 31-31-20 | D00327D | | H14 | | TB0145Y | C011 | BJ | | 050-099, 150-199, 275-276 | |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 59
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | |
| 573B | 24 | PW | WW | 5-0 | 31-31-20 | D00327D | H14 | | | | TB0145Y | C017 | BJ | | 277-299 | |
| 573R | 24 | PW | WW | 0-0 | 31-31-20 | D00327D | G14 | | | | TB0145Y | A011 | BJ | | 050-099, 150-199, 275-276 | |
| 573R | 24 | PW | WW | 0-0 | 31-31-20 | D00327D | G14 | | | | TB0145Y | A017 | BJ | | 277-299 | |
| 573Z | | | WW | 0-0 | 31-31-20 | D00327D | DED | | | | GDY0002 | S.. | 2 | | ALL | |
| 574B | 24 | PW | WX | 5-0 | 31-31-20 | D00327D | B15 | | | | TB0145Y | C012 | BJ | | 050-099, 150-199, 275-276 | |
| 574B | 24 | PW | WX | 5-0 | 31-31-20 | D00327D | B15 | | | | TB0145Y | C018 | BJ | | 277-299 | |
| 574R | 24 | PW | WX | 0-0 | 31-31-20 | D00327D | A15 | | | | TB0145Y | A012 | BJ | | 050-099, 150-199, 275-276 | |
| 574R | 24 | PW | WX | 0-0 | 31-31-20 | D00327D | A15 | | | | TB0145Y | A018 | BJ | | 277-299 | |
| 574Z | | | WX | 0-0 | 31-31-20 | D00327D | DED | | | | GDY0002 | S.. | 2 | | ALL | |
| 575B | 24 | PW | WY | 5-0 | 31-31-20 | D00327A | D15 | | | | TB0145Y | C103 | BJ | | 050-099, 150-199, 275-276 | |
| 575B | 24 | PW | WY | 5-0 | 31-31-20 | D00327A | D15 | | | | TB0145Y | C109 | BJ | | 277-299 | |
| 575R | 24 | PW | WY | 0-0 | 31-31-20 | D00327A | C15 | | | | TB0145Y | A103 | BJ | | 050-099, 150-199, 275-276 | |
| 575R | 24 | PW | WY | 0-0 | 31-31-20 | D00327A | C15 | | | | TB0145Y | A109 | BJ | | 277-299 | |
| 575Z | | | WY | 0-0 | 31-31-20 | D00327A | DED | | | | GDY0001 | S.. | 2 | | ALL | |
| 576B | 24 | PW | XA | 4-0 | 31-31-20 | D00327D | D15 | | | | TB0145Y | C034 | BJ | | ALL | |
| 576R | 24 | PW | XA | 0-0 | 31-31-20 | D00327D | C15 | | | | TB0145Y | A034 | BJ | | ALL | |
| 576Z | | | XA | 0-0 | 31-31-20 | D00327D | DED | | | | GDY0006 | S.. | 2 | | ALL | |
| 577B | 24 | PW | XB | 5-0 | 31-31-20 | D00327A | H14 | | | | TB0145Y | C101 | BJ | | 050-099, 150-199, 275-276 | |
| 577B | 24 | PW | XB | 5-0 | 31-31-20 | D00327A | H14 | | | | TB0145Y | C107 | BJ | | 277-299 | |
| 577R | 24 | PW | XB | 0-0 | 31-31-20 | D00327A | G14 | | | | TB0145Y | A101 | BJ | | 050-099, 150-199, 275-276 | |
| 577R | 24 | PW | XB | 0-0 | 31-31-20 | D00327A | G14 | | | | TB0145Y | A107 | BJ | | 277-299 | |
| 577Z | | | XB | 0-0 | 31-31-20 | D00327A | DED | | | | GDY0001 | S.. | 2 | | ALL | |
| 578B | 24 | PW | XC | 5-0 | 31-36-11 | D04765P | 25 | | | | D05753P | 52 | | | ALL | |
| 578R | 24 | PW | XC | 0-0 | 31-36-11 | D04765P | 24 | | | | D05753P | 51 | | | ALL | |
| 578Z | | | XC | 0-0 | 31-36-11 | D04765P | 26 | | | | D05753P | 50 | | | ALL | |
| 579 | 20 | UA | | 2-0 | 31-35-12 | GDX0007 | S.. | 2 | | | TB0145Y | REF | | XD | 050-099, 152-199, 275-299 | |
| 579B | 24 | PW | XD | 4-0 | 31-35-12 | D05753P | 29 | | | | TB0145Y | C143 | BJ | | ALL | |
| 579R | 24 | PW | XD | 0-0 | 31-35-12 | D05753P | 28 | | | | TB0145Y | A143 | BJ | | ALL | |
| 579Z | | | XD | 0-0 | 31-35-12 | D05753P | 30 | | | | TB0145Y | REF | | XD | 050-099, 152-199, 275-299 | |
| 579Z | | | XD | 0-0 | 31-35-12 | D05753P | 30 | | | | GDY0008 | S.. | 2 | | 150-151 | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 60

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | | |
| 580 | 20 | | UA | | 2-0 | 31-35-12 | GDX0007 | | S.. | 2 | | | TB0145Y | REF | | XE | 050-099, 152-199, 275-276 |
| 580B | 24 | PW | XE | | 4-0 | 31-35-12 | D05753P | | 32 | | | | TB0145Y | C144 | BJ | | ALL |
| 580R | 24 | PW | XE | | 0-0 | 31-35-12 | D05753P | | 31 | | | | TB0145Y | A144 | BJ | | ALL |
| 580Z | | | XE | | 0-0 | 31-35-12 | D05753P | | 33 | | | | TB0145Y | REF | | XE | 050-099, 152-199, 275-276 |
| 580Z | | | XE | | 0-0 | 31-35-12 | D05753P | | 33 | | | | GDY0008 | S.. | 2 | | 150-151, 277-299 |
| 581B | 24 | PW | XF | | 5-0 | 31-35-12 | D05753P | | 35 | | | | TB0145Y | C003 | BJ | | 050-099, 150-199, 275-276 |
| 581B | 24 | PW | XF | | 5-0 | 31-35-12 | D05753P | | 35 | | | | TB0145Y | C009 | BJ | | 277-299 |
| 581R | 24 | PW | XF | | 0-0 | 31-35-12 | D05753P | | 34 | | | | TB0145Y | A003 | BJ | | 050-099, 150-199, 275-276 |
| 581R | 24 | PW | XF | | 0-0 | 31-35-12 | D05753P | | 34 | | | | TB0145Y | A009 | BJ | | 277-299 |
| 581Z | | | XF | | 0-0 | 31-35-12 | D05753P | | 36 | | | | GDY0001 | S.. | 2 | | ALL |
| 582B | 24 | PW | XG | | 5-0 | 31-35-12 | D05753P | | 39 | | | | TB0145Y | C004 | BJ | | 050-099, 150-199, 275-276 |
| 582B | 24 | PW | XG | | 5-0 | 31-35-12 | D05753P | | 39 | | | | TB0145Y | C010 | BJ | | 277-299 |
| 582R | 24 | PW | XG | | 0-0 | 31-35-12 | D05753P | | 38 | | | | TB0145Y | A004 | BJ | | 050-099, 150-199, 275-276 |
| 582R | 24 | PW | XG | | 0-0 | 31-35-12 | D05753P | | 38 | | | | TB0145Y | A010 | BJ | | 277-299 |
| 582Z | | | XG | | 0-0 | 31-35-12 | D05753P | | 40 | | | | GDY0001 | S.. | 2 | | ALL |
| 583B | 24 | PW | XH | | 4-0 | 31-35-12 | D05753P | | 42 | | | | D05705J | 13 | | | ALL |
| 583R | 24 | PW | XH | | 0-0 | 31-35-12 | D05753P | | 41 | | | | D05705J | 12 | | | ALL |
| 583Z | | | XH | | 0-0 | 31-35-12 | D05753P | | 43 | | | | D05705J | 14 | | | ALL |
| 584B | 24 | PW | XI | | 4-0 | 31-35-12 | D05753P | | 47 | | | | D05705J | 20 | | | ALL |
| 584R | 24 | PW | XI | | 0-0 | 31-35-12 | D05753P | | 46 | | | | D05705J | 19 | | | ALL |
| 584Z | | | XI | | 0-0 | 31-35-12 | D05753P | | 48 | | | | D05705J | 21 | | | ALL |
| 585B | 24 | PW | XJ | | 4-0 | 31-35-12 | D05753P | | 26 | | | | D05705J | 23 | | | ALL |
| 585R | 24 | PW | XJ | | 0-0 | 31-35-12 | D05753P | | 25 | | | | D05705J | 22 | | | ALL |
| 585Z | | | XJ | | 0-0 | 31-35-12 | D05753P | | 27 | | | | D05705J | 24 | | | ALL |
| 586B | 24 | PW | XK | | 4-0 | 31-31-22 | TB0145Y | | C050 | BJ | | | D00327B | A14 | | | 050-099, 150-199, 275-276 |
| 586B | 24 | PW | XK | | 5-0 | 31-31-22 | TB0145Y | | C086 | BJ | | | D00327B | A14 | | | 277-278 |
| 586B | 24 | PW | XK | | 4-0 | 31-31-22 | TB0145Y | | C086 | BJ | | | D00327B | A14 | | | 280-299 |
| 586R | 24 | PW | XK | | 0-0 | 31-31-22 | TB0145X | | D048 | BJ | | | D00327B | A13 | | | 050-099, 150-199, 275-276 |
| 586R | 24 | PW | XK | | 0-0 | 31-31-22 | TB0145X | | D084 | BJ | | | D00327B | A13 | | | 277-299 |
| 586Z | | | XK | | 0-0 | 31-31-22 | GDY0009 | | S.. | 2 | | | D00327B | DED | | | 050-099, 150-199, 275-276 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 61
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | |
| 586Z | | | XK | 0-0 | 31-31-22 | GDY0013 | S.. | 2 | | D00327B | DED | | | 277-299 | | |
| 588B | 24 | PW | XM | 4-0 | 31-31-22 | TB0145Y | A049 | BJ | | D00327E | A11 | | | 050-099, 150-199, 275-276 | | |
| 588B | 24 | PW | XM | 5-0 | 31-31-22 | TB0145Y | A085 | BJ | | D00327E | A11 | | | 277-278 | | |
| 588B | 24 | PW | XM | 4-0 | 31-31-22 | TB0145Y | A085 | BJ | | D00327E | A11 | | | 280-299 | | |
| 588R | 24 | PW | XM | 0-0 | 31-31-22 | TB0145X | A048 | BJ | | D00327E | A10 | | | 050-099, 150-199, 275-276 | | |
| 588R | 24 | PW | XM | 0-0 | 31-31-22 | TB0145X | A084 | BJ | | D00327E | A10 | | | 277-299 | | |
| 588Z | | | XM | 0-0 | 31-31-22 | GDY0009 | S.. | 2 | | D00327E | DED | | | 050-099, 150-199, 275-276 | | |
| 588Z | | | XM | 0-0 | 31-31-22 | GDY0013 | S.. | 2 | | D00327E | DED | | | 277-299 | | |
| 589B | 24 | PW | XN | 4-0 | 31-31-22 | D05229P | | 36 | | TB0145Y | C049 | BJ | | 050-099, 150-199, 275-276 | | |
| 589B | 24 | PW | XN | 4-0 | 31-31-22 | D05229P | | 36 | | TB0145Y | C085 | BJ | | 277-278 | | |
| 589B | 24 | PW | XN | 5-0 | 31-31-22 | D05229P | | 36 | | TB0145Y | C085 | BJ | | 280-299 | | |
| 589R | 24 | PW | XN | 0-0 | 31-31-22 | D05229P | | 35 | | TB0145X | B048 | BJ | | 050-099, 150-199, 275-276 | | |
| 589R | 24 | PW | XN | 0-0 | 31-31-22 | D05229P | | 35 | | TB0145X | B084 | BJ | | 277-299 | | |
| 589Z | | | XN | 0-0 | 31-31-22 | D05229P | | 37 | | GDY0009 | S.. | 2 | | 050-099, 150-199, 275-276 | | |
| 589Z | | | XN | 0-0 | 31-31-22 | D05229P | | 37 | | GDY0013 | S.. | 2 | | 277-299 | | |
| 590B | 24 | PW | X0 | 4-0 | 31-31-22 | TB0145Y | C049 | BJ | | D00327B | A11 | | | 050-099, 150-199, 275-276 | | |
| 590B | 24 | PW | X0 | 5-0 | 31-31-22 | TB0145Y | C085 | BJ | | D00327B | A11 | | | 277-278 | | |
| 590B | 24 | PW | X0 | 4-0 | 31-31-22 | TB0145Y | C085 | BJ | | D00327B | A11 | | | 280-299 | | |
| 590R | 24 | PW | X0 | 0-0 | 31-31-22 | TB0145X | B048 | BJ | | D00327B | A10 | | | 050-099, 150-199, 275-276 | | |
| 590R | 24 | PW | X0 | 0-0 | 31-31-22 | TB0145X | B084 | BJ | | D00327B | A10 | | | 277-299 | | |
| 590Z | | | X0 | 0-0 | 31-31-22 | GDY0009 | S.. | 2 | | D00327B | DED | | | 050-099, 150-199, 275-276 | | |
| 590Z | | | X0 | 0-0 | 31-31-22 | GDY0013 | S.. | 2 | | D00327B | DED | | | 277-299 | | |
| 592B | 22 | PB | XQ | 4-0 | 31-31-25 | TB0145F | C070 | 2 | | D00327B | E07 | | | ALL | | |
| 592R | 22 | PB | XQ | 0-0 | 31-31-25 | TB0145F | A070 | 2 | | D00327B | E10 | | | ALL | | |
| 593B | 22 | PB | XR | 4-0 | 31-31-25 | TB0145G | | 69 | 2 | D00327B | E15 | | | ALL | | |
| 593R | 22 | PB | XR | 0-0 | 31-31-25 | TB0145G | | 69 | 2 | D00327B | E08 | | | ALL | | |
| 594B | 22 | PB | XS | 5-0 | 31-31-25 | D05227P | | 49 | | D00327E | C14 | | | 050-099, 150-199 | | |
| 594R | 22 | PB | XS | 0-0 | 31-31-25 | D05227P | | 48 | | D00327E | C13 | | | 050-099, 150-199 | | |
| 595B | 22 | PB | XT | 5-0 | 31-31-25 | D05227P | | 52 | | D00327E | C11 | | | 050-099, 150-199 | | |
| 595R | 22 | PB | XT | 0-0 | 31-31-25 | D05227P | | 51 | | D00327E | C10 | | | 050-099, 150-199 | | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 62

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | |
| 596B | 22 | PB | XU | 5-0 | 31-31-25 | D05227P | | 55 | | | D00327B | C14 | | | 050-099, 150-199 | |
| 596R | 22 | PB | XU | 0-0 | 31-31-25 | D05227P | | 54 | | | D00327B | C13 | | | 050-099, 150-199 | |
| 597 | 20 | UA | | 0-12 | 34-61-16 | GDY0010 | | S.. | 2 | | TB0145Z | REF | | XV | 050-099, 150-199, 275-276 | |
| 597B | 24 | PW | XV | 4-0 | 34-61-16 | D05733P | | 8 | | | TB0145Z | 58 | BJ | | 050-099, 150-199, 275-276 | |
| 597B | 24 | PW | XV | 4-0 | 34-61-16 | D05733P | | 8 | | | TB0145Z | 80 | BJ | | 277-299 | |
| 597R | 24 | PW | XV | 0-0 | 34-61-16 | D05733P | | 7 | | | TB0145Z | 57 | BJ | | 050-099, 150-199, 275-276 | |
| 597R | 24 | PW | XV | 0-0 | 34-61-16 | D05733P | | 7 | | | TB0145Z | 79 | BJ | | 277-299 | |
| 597Z | | | XV | 0-0 | 34-61-16 | D05733P | | 9 | | | TB0145Z | REF | | XV | 050-099, 150-199, 275-276 | |
| 597Z | | | XV | 0-0 | 34-61-16 | D05733P | | 9 | | | GDY0012 | S.. | 2 | | 277-299 | |
| 598 | 20 | UA | | 2-0 | 34-61-16 | GDX0011 | | S.. | 2 | | TB0145Y | REF | | XW | 157, 167-199 | |
| 598 | 20 | UA | | 2-0 | 34-61-16 | GDX0002 | | S.. | 2 | | TB0145Y | REF | | XW | 275-299 | |
| 598B | 24 | PW | XW | 4-0 | 34-61-16 | D05733P | | 11 | | | TB0145Y | C133 | BJ | | 050-099, 150-156, 162-166 | |
| 598B | 24 | PW | XW | 4-0 | 34-61-16 | D05733P | | 11 | | | TB0145Y | C180 | BJ | | 157, 167-199 | |
| 598B | 24 | PW | XW | 6-0 | 34-61-16 | D05733P | | 11 | | | TB0145Y | C020 | BJ | | 275-276 | |
| 598B | 24 | PW | XW | 4-0 | 34-61-16 | D05733P | | 11 | | | TB0145Y | C020 | BJ | | 277-278 | |
| 598B | 24 | PW | XW | 5-0 | 34-61-16 | D05733P | | 11 | | | TB0145Y | C020 | BJ | | 280-299 | |
| 598R | 24 | PW | XW | 0-0 | 34-61-16 | D05733P | | 10 | | | TB0145Y | A133 | BJ | | 050-099, 150-156, 162-166 | |
| 598R | 24 | PW | XW | 0-0 | 34-61-16 | D05733P | | 10 | | | TB0145Y | A180 | BJ | | 157, 167-199 | |
| 598R | 24 | PW | XW | 0-0 | 34-61-16 | D05733P | | 10 | | | TB0145Y | A020 | BJ | | 275-299 | |
| 598Z | | | XW | 0-0 | 34-61-16 | D05733P | | 12 | | | GDY0006 | S.. | 2 | | 050-099, 150-156, 162-166 | |
| 598Z | | | XW | 0-0 | 34-61-16 | D05733P | | 12 | | | TB0145Y | REF | | XW | 157, 167-199, 275-299 | |
| 599 | 20 | UA | | 2-0 | 34-61-16 | GDX0006 | | S.. | 2 | | TB0145Y | REF | | XX | 050-099, 152-199, 275-299 | |
| 599B | 24 | PW | XX | 4-0 | 34-61-16 | D05427P | | 2 | | | TB0145Y | C043 | BJ | | ALL | |
| 599R | 24 | PW | XX | 0-0 | 34-61-16 | D05427P | | 1 | | | TB0145Y | A043 | BJ | | ALL | |
| 599Z | | | XX | 0-0 | 34-61-16 | D05427P | | 3 | | | TB0145Y | REF | | XX | 050-099, 152-199, 275-299 | |
| 599Z | | | XX | 0-0 | 34-61-16 | D05427P | | 3 | | | GDY0008 | S.. | 2 | | 150-151 | |
| 600 | 20 | UA | | 2-0 | 34-61-14 | GDX0010 | | S.. | 2 | | TB0145Y | REF | | XZ | 157, 167-199 | |
| 600 | 20 | UA | | 2-0 | 34-61-14 | TB0145Y | | REF | | XZ | GDX0010 | S.. | 2 | | 275-276 | |
| 600B | 24 | PW | XZ | 5-0 | 34-61-14 | D06199P | | 4 | | | TB0145Y | C075 | BJ | | 157, 167-199 | |
| 600B | 24 | PW | XZ | 7-0 | 34-61-14 | TB0145Y | | C075 | BJ | | D06199P | 4 | | | 275-276 | |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 63
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | | |
| 600B | 24 | PW | XZ | 5-0 | 34-61-14 | D06199P | | 4 | | | | | TB0145Y | C073 | BJ | | 277-299 |
| 600R | 24 | PW | XZ | 0-0 | 34-61-14 | D06199P | | 3 | | | | | TB0145Y | A075 | BJ | | 157, 167-199 |
| 600R | 24 | PW | XZ | 0-0 | 34-61-14 | TB0145Y | A075 | BJ | | | | | D06199P | 3 | | | 275-276 |
| 600R | 24 | PW | XZ | 0-0 | 34-61-14 | D06199P | | 3 | | | | | TB0145Y | A073 | BJ | | 277-299 |
| 600Z | | | XZ | 0-0 | 34-61-14 | D06199P | | 5 | | | | | TB0145Y | REF | | XZ | 157, 167-199 |
| 600Z | | | XZ | 0-0 | 34-61-14 | TB0145Y | REF | | | | XZ | | D06199P | 5 | | | 275-276 |
| 600Z | | | XZ | 0-0 | 34-61-14 | D06199P | | 5 | | | | | GDY0011 | S.. | 2 | | 277-299 |
| 601 | 24 | PK | | 3-0 | 31-31-16 | D00327D | | G09 | | | | | D01421 | 1 | | | 050, 275-299 |
| 602 | 24 | PK | | 3-0 | 31-31-16 | D00327D | | H09 | | | | | D01421 | 2 | | | 050-099 |
| 605 | 24 | PK | | 3-0 | 31-31-16 | D00327D | | A11 | | | | | D01421 | 5 | | | 050, 150, 152, 154, 156, 162, 164, 166, 275, 277 |
| 606 | 24 | PK | | 3-0 | 31-31-17 | D00327D | | B11 | | | | | D01421 | 6 | | | 051-099 |
| 606 | 24 | PK | | 3-0 | 31-31-16 | D00327D | | B11 | | | | | D01421 | 6 | | | 151-152, 155-156, 163-164, 167-199, 276-277 |
| 606 | 24 | PK | | 3-0 | 31-31-16 | D00327D | | B11 | | | | | D01421 | CAP | Y | | 280-299 |
| 607 | 24 | PK | | 3-0 | 31-31-16 | D00327D | | C11 | | | | | D01421 | 7 | | | 153-156, 162-164, 278-299 |
| 608 | 24 | PK | | 3-0 | 31-31-16 | D00327D | | D11 | | | | | D01421 | 8 | | | 157-164, 280-299 |
| 609 | 24 | PK | | 3-0 | 31-31-16 | D00327D | | E11 | | | | | D01421 | 9 | | | 165-199 |
| 613 | 24 | PK | | 3-0 | 31-31-16 | D00327D | | K11 | | | | | D01421 | 13 | | | ALL |
| 614 | 24 | PK | | 3-0 | 31-31-16 | D00327D | | A09 | | | | | D01421 | 14 | | | ALL |
| 618 | 24 | PK | | 3-0 | 31-31-16 | D00327D | | E09 | | | | | D01421 | 18 | | | 150-199, 275-299 |
| 643 | 24 | PK | | 3-0 | 31-31-19 | D05703P | | 44 | | | | | D00327D | J03 | | | ALL |
| 652 | 24 | PK | | 4-0 | 31-31-19 | D00327D | | E01 | | | | | TB0145X | A042 | BJ | | ALL |
| 653 | 24 | PK | | 4-0 | 31-31-19 | D00327D | | F01 | | | | | TB0145X | B042 | BJ | | ALL |
| 655 | 24 | PK | | 4-0 | 31-31-19 | D00327D | | H01 | | | | | TB0145Y | A168 | BJ | | ALL |
| 657 | 22 | PA | | 4-0 | 31-31-18 | TB0145X | A037 | BJ | | | | | D00327A | E07 | | | ALL |
| 658 | 22 | PA | | 4-0 | 31-31-18 | TB0145X | C037 | BJ | | | | | D00327D | F07 | | | ALL |
| 660 | 24 | PK | | 4-0 | 31-31-19 | D00327D | A01 | | | | | | D05229P | 24 | | | ALL |
| 662 | 22 | PA | | 6-0 | 31-31-15 | D04731P | | 1 | | | | | TB0145Z | 153 | BJ | | ALL |
| 664 | 22 | PA | | 3-0 | 31-31-15 | D00327B | | F06 | | | | | GDY0009 | A.. | 2 | | ALL |
| 665 | 22 | PA | | 6-0 | 31-31-15 | D04731P | | 2 | | | | | TB0145Z | 153 | BJ | | ALL |
| 666 | 22 | PA | | 3-0 | 31-31-15 | GDY0009 | | A.. | 2 | | | | D00327B | A08 | | | ALL |
| 667 | 22 | PA | | 6-0 | 31-31-15 | D04731P | | 3 | | | | | TB0145Z | 153 | BJ | | ALL |
| 668 | 22 | PA | | 3-0 | 31-31-15 | GDY0009 | | A.. | 2 | | | | D00327E | A08 | | | ALL |
| 671 | 22 | PA | | 5-0 | 31-31-15 | D04215P | | 7 | | | | | TB0145Z | 153 | BJ | | ALL |
| 672 | 24 | PK | | 4-5 | 34-12-62 | D05227P | | 14 | | | | | TB0145Y | A186 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 64

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|---------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | |
| 681 | 20 | | UA | | 2-0 | 34-61-14 | GDX0010 | S.. | 2 | | TB0145Y | REF | | D1 | 157, 167-199, 275-276 |
| 681 | 20 | | UA | | 2-0 | 34-61-14 | GDX0002 | S.. | 2 | | TB0145Y | REF | | D1 | 277-299 |
| 681B | 24 | | PW | D1 | 4-0 | 34-61-14 | D05733P | | 30 | | TB0145Y | C077 | BJ | | 157, 167-199 |
| 681B | 24 | | PW | D1 | 7-0 | 34-61-14 | D05733P | | 30 | | TB0145Y | C077 | BJ | | 275-276 |
| 681B | 24 | | PW | D1 | 5-0 | 34-61-14 | D05733P | | 30 | | TB0145Y | C019 | BJ | | 277-299 |
| 681R | 24 | | PW | D1 | 0-0 | 34-61-14 | D05733P | | 29 | | TB0145Y | A077 | BJ | | 157, 167-199, 275-276 |
| 681R | 24 | | PW | D1 | 0-0 | 34-61-14 | D05733P | | 29 | | TB0145Y | A019 | BJ | | 277-299 |
| 681Z | | | | D1 | 0-0 | 34-61-14 | D05733P | | 31 | | TB0145Y | REF | | D1 | 157, 167-199, 275-299 |
| 682 | 24 | | PK | | 5-0 | 34-61-17 | D06199P | | 6 | | TB0145D | A088 | 2 | | 157, 167-199 |
| 682 | 24 | | PK | | 6-0 | 34-61-17 | D06199P | | 6 | | TB0145D | A089 | 2 | | 275-276 |
| 682 | 24 | | PK | | 4-0 | 34-61-17 | D06199P | | 6 | | TB0145D | A089 | 2 | | 277-278 |
| 682 | 24 | | PK | | 5-0 | 34-61-17 | D06199P | | 6 | | TB0145D | A089 | 2 | | 280-299 |
| 685 | 22 | | PA | | 4-0 | 34-22-38 | D05733P | | 45 | | TB0145Y | A044 | BJ | | ALL |
| 700 | 20 | | PA | | 4-0 | 31-31-11 | TB0145Z | | 131 | BJ | TB0145Z | 138 | BJ | | ALL |
| 706 | 24 | | PK | | 4-0 | 31-31-19 | D00327D | | G01 | | TB0145Y | C168 | BJ | | ALL |
| 718 | 24 | | PK | | 3-0 | 31-31-19 | TB0145R | | C022 | 2 | * | TB0145R | A018 | 2 | 050-099 |
| 718 | 24 | | PK | | 4-0 | 31-31-19 | TB0145R | | C022 | 2 | * | TB0145R | A018 | 2 | 150-199, 275-276 |
| 718 | 24 | | PK | | 4-0 | 31-31-19 | TB0145R | | C001 | 2 | * | TB0145R | A006 | 2 | 277-278 |
| 718 | 24 | | PK | | 3-0 | 31-31-19 | TB0145R | | C001 | 2 | * | TB0145R | A006 | 2 | 280-299 |
| 719 | 24 | | PK | | 4-0 | 31-31-19 | TB0145R | | C018 | 2 | | TB0145Y | A019 | BJ | 050-099, 150-199, 275-276 |
| 719 | 24 | | PK | | 4-0 | 31-31-19 | TB0145R | | C006 | 2 | | TB0145G | 2 | 2 | 277-278 |
| 719 | 24 | | PK | | 3-0 | 31-31-19 | TB0145R | | C006 | 2 | | TB0145G | 2 | 2 | 280-299 |
| 720 | 24 | | PK | | 4-0 | 31-31-19 | TB0145R | | C017 | 2 | | TB0145Y | A019 | BJ | 050-099, 150-199, 275-276 |
| 720 | 24 | | PK | | 4-0 | 31-31-19 | TB0145R | | C004 | 2 | | TB0145G | 2 | 2 | 277-278 |
| 720 | 24 | | PK | | 3-0 | 31-31-19 | TB0145R | | C004 | 2 | | TB0145G | 2 | 2 | 280-299 |
| 721 | 24 | | PK | | 3-0 | 31-31-19 | TB0145R | | C021 | 2 | * | TB0145R | A017 | 2 | 050-099 |
| 721 | 24 | | PK | | 4-0 | 31-31-19 | TB0145R | | C021 | 2 | * | TB0145R | A017 | 2 | 150-199, 275-276 |
| 721 | 24 | | PK | | 4-0 | 31-31-19 | TB0145R | | C003 | 2 | * | TB0145R | A004 | 2 | 277-278 |
| 721 | 24 | | PK | | 3-0 | 31-31-19 | TB0145R | | C003 | 2 | * | TB0145R | A004 | 2 | 280-299 |
| 722 | 24 | | PK | | 5-0 | 31-31-21 | D04711P | | 32 | | D00327A | C07 | | | ALL |
| 723 | 24 | | PK | | 5-0 | 31-31-21 | D04711P | | 34 | | TB0145R | A028 | 2 | | 050-099, 150-199, 275-276 |
| 723 | 24 | | PK | | 5-0 | 31-31-21 | D04711P | | 34 | | TB0145R | A105 | 2 | | 277-299 |
| 724 | 24 | | PK | | 4-0 | 31-31-21 | TB0145R | | A028 | 2 | | TB0145R | A027 | 2 | 050-099, 150-199, 275-276 |
| 724 | 24 | | PK | | 4-0 | 31-31-21 | TB0145R | | A105 | 2 | | TB0145R | A104 | 2 | 277-278 |
| 724 | 24 | | PK | | 3-0 | 31-31-21 | TB0145R | | A105 | 2 | | TB0145R | A104 | 2 | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 65
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | |
| 725 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C028 | 2 | | D00327D | D07 | | | 050-099, 150-199, 275-276 | | |
| 725 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C105 | 2 | | D00327D | D07 | | | 277-299 | | |
| 726 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C028 | 2 | | D05229P | 29 | | | 050-099, 150-199, 275-276 | | |
| 726 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C105 | 2 | | D05229P | 29 | | | 277-299 | | |
| 728 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C027 | 2 | | D00327D | C07 | | | 050-099, 150-199, 275-276 | | |
| 728 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C104 | 2 | | D00327D | C07 | | | 277-299 | | |
| 729 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C027 | 2 | | D05229P | 28 | | | 050-099, 150-199, 275-276 | | |
| 729 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C104 | 2 | | D05229P | 28 | | | 277-299 | | |
| 739 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | A023 | 2 | | D05753P | 4 | | | 050-099, 150-199, 275-276 | | |
| 739 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | A005 | 2 | | D05753P | 4 | | | 277-299 | | |
| 740 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C023 | 2 | * | D00327E | C07 | | | 050-099, 150-199, 275-276 | | |
| 740 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C005 | 2 | * | D00327E | C07 | | | 277-299 | | |
| 741 | 24 | | PK | 4-0 | 31-31-21 | TB0145R | C023 | 2 | * | TB0145R | A024 | 2 | | 050-099, 150-199, 275-276 | | |
| 741 | 24 | | PK | 3-0 | 31-31-21 | TB0145R | C005 | 2 | * | TB0145R | A101 | 2 | | 277-299 | | |
| 742 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C024 | 2 | * | D05753P | 5 | | | 050-099, 150-199, 275-276 | | |
| 742 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C101 | 2 | * | D05753P | 5 | | | 277-299 | | |
| 743 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C024 | 2 | * | D00327E | C08 | | | 050-099, 150-199, 275-276 | | |
| 743 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C101 | 2 | * | D00327E | C08 | | | 277-299 | | |
| 744 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C025 | 2 | * | D00327B | C10 | | | 050-099, 150-199, 275-276 | | |
| 744 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C102 | 2 | * | D00327B | C10 | | | 277-299 | | |
| 745 | 24 | | PK | 4-0 | 31-31-21 | TB0145R | C025 | 2 | * | TB0145R | A026 | 2 | | 050-099, 150-199, 275-276 | | |
| 745 | 24 | | PK | 4-0 | 31-31-21 | TB0145R | C102 | 2 | * | TB0145R | A103 | 2 | | 277-278 | | |
| 745 | 24 | | PK | 3-0 | 31-31-21 | TB0145R | C102 | 2 | * | TB0145R | A103 | 2 | | 280-299 | | |
| 746 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C026 | 2 | * | D00327B | C11 | | | 050-099, 150-199, 275-276 | | |
| 746 | 24 | | PK | 5-0 | 31-31-21 | TB0145R | C103 | 2 | * | D00327B | C11 | | | 277-299 | | |
| 747 | 24 | | PK | 5-0 | 31-31-22 | D05753P | 6 | | | D00327D | E03 | | | ALL | | |
| 748 | 24 | | PK | 4-0 | 31-31-22 | TB0145X | A162 | BJ | | D00327A | A05 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 66

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|---------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | |
| 749 | 24 | | PK | | 5-0 | 31-31-22 | D06594P | | | | D00327D | H03 | | | ALL |
| 750 | 24 | | PK | | 6-0 | 31-31-22 | D06594P | | | | TB0145Z | 138 | BJ | | 050-099, 275-299 |
| 750 | 24 | | PK | | 5-0 | 31-31-22 | D06594P | | | | TB0145Z | 138 | BJ | | 150-199 |
| 751 | 24 | | PK | | 5-0 | 31-31-22 | D06594P | | | | D00327A | G03 | | | ALL |
| 753 | 22 | | PA | | 5-0 | 31-35-11 | D04215P | | | | TB0145Y | A130 | BJ | | 050-099, 150-154, 275-299 |
| 753 | 22 | | PA | | 4-0 | 31-35-11 | D04215P | | | | D05753P | 44 | | | 155-157 |
| 753 | 22 | | PA | | 5-0 | 31-35-11 | D04215P | | | | D05753P | 44 | | | 162-199 |
| 762 | 22 | | PA | | 4-0 | 31-35-11 | D05753P | | | | TB0145Y | A130 | BJ | | 050-099, 150-154, 275-299 |
| 771 | 22 | | PA | | 6-0 | 31-31-22 | D06594P | | | 4 | TB0145Z | 165 | BJ | | ALL |
| 772 | 22 | | PA | | 5-0 | 31-31-22 | TB0145Z | | | 153 | BJ | 165 | BJ | | ALL |
| 773 | 22 | | PA | | 6-0 | 31-31-22 | D06594P | | | 5 | TB0145Z | 165 | BJ | | ALL |
| 774 | 22 | | PA | | 4-0 | 31-31-22 | TB0145Z | | | 165 | BJ | D00327E | A15 | | ALL |
| 778B | 24 | | PW | N8 | 6-0 | 31-31-22 | D06594P | | | 2 | TB0145Y | A050 | BJ | | 050-099, 150-199, 275-276 |
| 778B | 24 | | PW | N8 | 5-0 | 31-31-22 | D06594P | | | 2 | TB0145Y | A086 | BJ | | 277-299 |
| 778R | 24 | | PW | N8 | 0-0 | 31-31-22 | D06594P | | | 1 | TB0145X | C048 | BJ | | 050-099, 150-199, 275-276 |
| 778R | 24 | | PW | N8 | 0-0 | 31-31-22 | D06594P | | | 1 | TB0145X | C084 | BJ | | 277-299 |
| 778Z | | | | N8 | 0-0 | 31-31-22 | D06594P | | | 3 | GDY0009 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 778Z | | | | N8 | 0-0 | 31-31-22 | D06594P | | | 3 | GDY0013 | S.. | 2 | | 277-299 |
| 779B | 24 | | PW | N9 | 6-0 | 31-31-22 | D06594P | | | 7 | TB0145Y | C050 | BJ | | 050-099, 150-199, 275-276 |
| 779B | 24 | | PW | N9 | 5-0 | 31-31-22 | D06594P | | | 7 | TB0145Y | C086 | BJ | | 277-299 |
| 779R | 24 | | PW | N9 | 0-0 | 31-31-22 | D06594P | | | 6 | TB0145X | D048 | BJ | | 050-099, 150-199, 275-276 |
| 779R | 24 | | PW | N9 | 0-0 | 31-31-22 | D06594P | | | 6 | TB0145X | D084 | BJ | | 277-299 |
| 779Z | | | | N9 | 0-0 | 31-31-22 | D06594P | | | 8 | GDY0009 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 779Z | | | | N9 | 0-0 | 31-31-22 | D06594P | | | 8 | GDY0013 | S.. | 2 | | 277-299 |
| 782 | 24 | | PK | | 5-0 | 31-35-11 | D04725P | | | 28 | D05753P | 45 | | | ALL |
| 783 | 24 | | PK | | 5-0 | 31-31-21 | TB0145R | | | A027 | 2 | TB0145Z | 131 | BJ | 050-099, 150-199, 275-276 |
| 783 | 24 | | PK | | 5-0 | 31-31-21 | TB0145R | | | A104 | 2 | TB0145Z | 131 | BJ | 277-299 |
| 784 | 22 | | PA | | 5-0 | 31-31-25 | D05227P | | | 47 | TB0145Z | 137 | BJ | | 050-099, 150-199 |
| 785 | 22 | | PA | | 4-0 | 31-31-25 | D00327E | | | C15 | | TB0145Z | 137 | BJ | 050-099, 150-199 |
| 786 | 22 | | PA | | 5-0 | 31-31-25 | D05227P | | | 50 | TB0145Z | 137 | BJ | | 050-099, 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 67
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|----|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | | | | |
| 787 | 22 | | PA | | 4-0 | 31-31-25 | TB0145Z | | 137 | BJ | | | | D00327E | C12 | | | | 050-099, 150-199 |
| 788 | 22 | | PA | | 5-0 | 31-31-25 | D05227P | | 53 | | | | | TB0145Z | 137 | BJ | | | 050-099, 150-199 |
| 789 | 22 | | PA | | 4-0 | 31-31-25 | TB0145Z | | 153 | BJ | | | | D00327B | C15 | | | | 050-099, 150-199 |
| 792 | 20 | | UA | | 2-0 | 34-61-24 | GDX0006 | | S.. | 2 | | | | TB0145Y | REF | | P2 | | 050-099, 152-199, 275-299 |
| 792B | 24 | | PW | P2 | 4-0 | 34-61-24 | D05229P | | 20 | | | | | TB0145Y | C043 | BJ | | | ALL |
| 792R | 24 | | PW | P2 | 0-0 | 34-61-24 | D05229P | | 19 | | | | | TB0145Y | A043 | BJ | | | ALL |
| 792Z | | | | P2 | 0-0 | 34-61-24 | D05229P | | 21 | | | | | TB0145Y | REF | | P2 | | 050-099, 152-199, 275-299 |
| 792Z | | | | P2 | 0-0 | 34-61-24 | D05229P | | 21 | | | | | GDY0008 | S.. | 2 | | | 150-151 |
| 793 | 20 | | UA | | 2-0 | 31-31-13 | GDX0007 | | S.. | 2 | | | | TB0145Y | REF | | P3 | | 050-099, 152-199, 275-276 |
| 793B | 24 | | PW | P3 | 6-0 | 31-31-13 | TB0145Y | | C144 | BJ | | | | D05227P | 9 | | | | ALL |
| 793R | 24 | | PW | P3 | 0-0 | 31-31-13 | TB0145Y | | A144 | BJ | | | | D05227P | 8 | | | | ALL |
| 793Z | | | | P3 | 0-0 | 31-31-13 | TB0145Y | | REF | | P3 | | | D05227P | 10 | | | | 050-099, 152-199, 275-276 |
| 793Z | | | | P3 | 0-0 | 31-31-13 | GDY0008 | | S.. | 2 | | | | D05227P | 10 | | | | 150-151, 277-299 |
| 794B | 24 | | PW | P4 | 8-0 | 31-31-14 | TB0145Y | | C003 | BJ | | | | D04943P | 1 | | | | 050-099, 150-199, 275-276 |
| 794B | 24 | | PW | P4 | 8-0 | 31-31-14 | TB0145Y | | C009 | BJ | | | | D04943P | 1 | | | | 277-299 |
| 794R | 24 | | PW | P4 | 0-0 | 31-31-14 | TB0145Y | | A003 | BJ | | | | D04943P | 2 | | | | 050-099, 150-199, 275-276 |
| 794R | 24 | | PW | P4 | 0-0 | 31-31-14 | TB0145Y | | A009 | BJ | | | | D04943P | 2 | | | | 277-299 |
| 794Z | | | | P4 | 0-0 | 31-31-14 | GDY0001 | | S.. | 2 | | | | D04943P | 3 | | | | ALL |
| 795 | 22 | | PA | | 4-0 | 31-31-18 | TB0145X | | D037 | BJ | | | | D00327D | K07 | | | | ALL |
| 796 | 22 | | PA | | 4-0 | 31-31-18 | TB0145X | | B037 | BJ | | | | D00327A | K07 | | | | ALL |
| 797 | 24 | | PK | | 4-0 | 31-31-19 | D00327A | | A07 | | | | | TB0145X | A047 | BJ | | | 050-099, 150-199, 275-276 |
| 797 | 24 | | PK | | 4-0 | 31-31-19 | D00327A | | A07 | | | | | TB0145X | A083 | BJ | | | 277-299 |
| 798 | 24 | | PK | | 7-0 | 31-31-13 | D00327D | | H15 | | | | | D05733P | 13 | | | | ALL |
| 799 | 22 | | PA | | 4-0 | 31-31-25 | TB0145Z | | 137 | BJ | | | | TB0145Z | 153 | BJ | | | 050-099, 150-199 |
| 804B | 24 | | PW | Q4 | 4-0 | 31-35-12 | D05753P | | 8 | | | | | TB0145Y | C029 | BJ | | | ALL |
| 804R | 24 | | PW | Q4 | 0-0 | 31-35-12 | D05753P | | 7 | | | | | TB0145Y | A029 | BJ | | | ALL |
| 804Z | | | | Q4 | 0-0 | 31-35-12 | D05753P | | 9 | | | | | GDY0006 | S.. | 2 | | | ALL |
| 809 | 24 | | PK | | 5-0 | 34-61-25 | D05229P | | 18 | | | | | TB0145X | D169 | BJ | | | ALL |
| 810 | 24 | | PK | | 5-0 | 31-31-26 | D05207P | | 29 | | | | | D00327D | G03 | | | | ALL |
| 811 | 24 | | PK | | 5-0 | 31-31-26 | D05207P | | 24 | | | | | D00327A | D01 | | | | ALL |
| 812 | 24 | | PK | | 4-0 | 31-31-26 | TB0145R | | A071 | 2 | | * | | D00327D | G15 | | | | 050-099 |
| 812 | 24 | | PK | | 5-0 | 31-31-26 | TB0145R | | A071 | 2 | | | | D00327D | G15 | | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 68

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | |
| 812 | 24 | | PK | 4-0 | 31-31-26 | TB0145R | A071 | 2 | | D00327D | G15 | | | 275-276 | | |
| 812 | 24 | | PK | 4-0 | 31-31-26 | TB0145R | A090 | 2 | | D00327D | G15 | | | 277-299 | | |
| 813 | 24 | | PK | 4-0 | 31-31-26 | TB0145R | A073 | 2 | | D00327A | J12 | | | 050-099, 275-276 | | |
| 813 | 24 | | PK | 5-0 | 31-31-26 | TB0145R | A073 | 2 | | D00327A | J12 | | | 150-199 | | |
| 813 | 24 | | PK | 4-0 | 31-31-26 | TB0145R | A091 | 2 | | D00327A | J12 | | | 277-299 | | |
| 815 | 24 | | PK | 4-0 | 31-31-26 | D04711P | | 36 | | D00327D | G07 | | | ALL | | |
| 816 | 24 | | PK | 4-0 | 31-31-26 | D04711P | | 37 | | D00327A | H07 | | | ALL | | |
| 817 | 24 | | PK | 5-0 | 31-31-26 | TB0145X | A105 | BJ | | D00327D | J11 | | | 050-099, 150-199, 275-276 | | |
| 817 | 24 | | PK | 5-0 | 31-31-26 | TB0145X | A111 | BJ | | D00327D | J11 | | | 277-299 | | |
| 818 | 24 | | PK | 5-0 | 31-31-26 | TB0145X | B105 | BJ | | D00327A | D07 | | | 050-099, 150-199, 275-276 | | |
| 818 | 24 | | PK | 5-0 | 31-31-26 | TB0145X | B111 | BJ | | D00327A | D07 | | | 277-299 | | |
| 819 | 24 | | PK | 5-0 | 31-31-26 | TB0145X | C105 | BJ | | D00327A | B07 | | | 050-099, 150-199, 275-276 | | |
| 819 | 24 | | PK | 5-0 | 31-31-26 | TB0145X | C111 | BJ | | D00327A | B07 | | | 277-299 | | |
| 820 | 24 | | PK | 5-0 | 31-31-26 | TB0145X | D105 | BJ | | D00327D | E07 | | | 050-099, 150-199, 275-276 | | |
| 820 | 24 | | PK | 5-0 | 31-31-26 | TB0145X | D111 | BJ | | D00327D | E07 | | | 277-299 | | |
| 822 | 24 | | PK | 5-0 | 31-31-26 | TB0145X | B107 | BJ | | D00327D | J07 | | | 050-099, 150-199, 275-276 | | |
| 822 | 24 | | PK | 5-0 | 31-31-26 | TB0145X | B113 | BJ | | D00327D | J07 | | | 277-299 | | |
| 823 | 24 | | PK | 5-0 | 31-31-26 | TB0145X | C107 | BJ | | D00327A | G05 | | | 050-099, 150-199, 275-276 | | |
| 823 | 24 | | PK | 5-0 | 31-31-26 | TB0145X | C113 | BJ | | D00327A | G05 | | | 277-299 | | |
| 824 | 20 | | PA | 5-0 | 31-31-22 | TB0145Y | A049 | BJ | | GDY0013 | S.. | 2 | | 050-099, 150-199, 275-276 | | |
| 824 | 20 | | PA | 3-0 | 31-31-22 | TB0145Y | A085 | BJ | | GDY0013 | S.. | 2 | | 277-278 | | |
| 824 | 20 | | PA | 5-0 | 31-31-22 | TB0145Y | A085 | BJ | | GDY0013 | S.. | 2 | | 280-299 | | |
| 825 | 20 | | PA | 5-0 | 31-31-22 | TB0145Y | C049 | BJ | | GDY0013 | S.. | 2 | | 050-099, 150-199, 275-276 | | |
| 825 | 20 | | PA | 3-0 | 31-31-22 | TB0145Y | C085 | BJ | | GDY0013 | S.. | 2 | | 277-299 | | |
| 827 | 20 | | PA | 5-0 | 31-31-22 | TB0145Y | A050 | BJ | | GDY0013 | S.. | 2 | | 050-099, 150-199, 275-276 | | |
| 827 | 20 | | PA | 3-0 | 31-31-22 | TB0145Y | A086 | BJ | | GDY0013 | S.. | 2 | | 277-299 | | |
| 828 | 20 | | PA | 5-0 | 31-31-22 | TB0145Y | C050 | BJ | | GDY0013 | S.. | 2 | | 050-099, 150-199, 275-276 | | |
| 828 | 20 | | PA | 3-0 | 31-31-22 | TB0145Y | C086 | BJ | | GDY0013 | S.. | 2 | | 277-299 | | |
| 832 | 24 | | PK | 4-0 | 34-61-16 | D05427P | | 8 | | TB0145Y | A140 | BJ | | ALL | | |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 69
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | |
| 833B | 24 | PW | T3 | 4-0 | 34-45-12 | D05207P | | 46 | | | | TB0145X | B119 | BJ | | 050-099, 150-152, 155-199 |
| 833B | 24 | PW | V3 | 4-0 | 34-45-12 | D05207P | | 26 | | | | TB0145X | B119 | BJ | | 153-154 |
| 833B | 24 | PW | T3 | 4-0 | 34-45-12 | D05207P | | 46 | | | | TB0145X | B124 | BJ | | 277-299 |
| 833R | 24 | PW | T3 | 0-0 | 34-45-12 | D05207P | | 45 | | | | TB0145X | B118 | BJ | | 050-099, 150-152, 155-199 |
| 833R | 24 | PW | V3 | 0-0 | 34-45-12 | D05207P | | 25 | | | | TB0145X | B118 | BJ | | 153-154 |
| 833R | 24 | PW | T3 | 0-0 | 34-45-12 | D05207P | | 45 | | | | TB0145X | B123 | BJ | | 277-299 |
| 833Z | | | T3 | 0-0 | 34-45-12 | D05207P | | 47 | | | | TB0145X | REF | | T3 | 050-099, 150-152, 155-199, 277-299 |
| 833Z | | | V3 | 0-0 | 34-45-12 | D05207P | | 27 | | | | TB0145X | REF | | V3 | 153-154 |
| 834 | 24 | PK | | 4-0 | 31-35-11 | D05703P | | 43 | | | | TB0145Y | C140 | BJ | | ALL |
| 840 | 20 | UA | | 1-6 | 34-61-11 | TB0145Y | REF | | U0 | | | GDY0012 | S.. | 2 | | 050-099, 275-276 |
| 840 | 20 | UA | | 4-0 | 34-61-11 | TB0145Y | REF | | U0 | | | GDY0012 | S.. | 2 | | 151-152, 154, 156-157 |
| 840B | 24 | PW | U0 | 5-0 | 34-61-11 | D05427P | | 6 | | | | TB0145Y | C179 | BJ | | ALL |
| 840R | 24 | PW | U0 | 0-0 | 34-61-11 | D05427P | | 5 | | | | TB0145Y | A179 | BJ | | ALL |
| 840Z | | | U0 | 0-0 | 34-61-11 | D05427P | | 4 | | | | TB0145Y | REF | | U0 | 050-099, 151-152, 154, 156-157, 275-276 |
| 840Z | | | U0 | 0-0 | 34-61-11 | D05427P | | 4 | | | | GDY0012 | S.. | 2 | | 150, 153, 155, 162-199, 277-299 |
| 841 | 24 | PK | | 5-0 | 31-31-26 | D05427P | | 7 | | | | TB0145R | A071 | 2 | * | 050-099 |
| 841 | 24 | PK | | 5-0 | 31-31-26 | D05427P | | 7 | | | | TB0145R | A071 | 2 | | 150-199, 275-276 |
| 841 | 24 | PK | | 5-0 | 31-31-26 | D05427P | | 7 | | | | TB0145R | A090 | 2 | | 277-299 |
| 842 | 24 | PK | | 4-0 | 31-31-26 | TB0145R | | C073 | 2 | | | GDY0012 | D.. | 2 | | 050-099, 150-199, 275-276 |
| 842 | 24 | PK | | 3-0 | 31-31-26 | TB0145R | | C091 | 2 | | | GDY0013 | D.. | 2 | | 277-299 |
| 843 | 24 | PK | | 4-0 | 31-31-26 | TB0145R | | C071 | 2 | | | GDY0012 | D.. | 2 | | 050-099, 150-199, 275-276 |
| 843 | 24 | PK | | 3-0 | 31-31-26 | TB0145R | | C090 | 2 | | | GDY0013 | D.. | 2 | | 277-299 |
| 844B | 24 | PW | U4 | 7-0 | 34-61-15 | D06223P | | 5 | | | | D05733P | 51 | | | ALL |
| 844R | 24 | PW | U4 | 0-0 | 34-61-15 | D06223P | | 4 | | | | D05733P | 50 | | | ALL |
| 844Z | | | U4 | 0-0 | 34-61-15 | D06223P | | 6 | | | | D05733P | 52 | | | ALL |
| 845B | 24 | PW | U5 | 7-0 | 34-61-15 | D06223P | | 8 | | | | D05733P | 54 | | | ALL |
| 845R | 24 | PW | U5 | 0-0 | 34-61-15 | D06223P | | 7 | | | | D05733P | 53 | | | ALL |
| 845Z | | | U5 | 0-0 | 34-61-15 | D06223P | | 9 | | | | D05733P | 55 | | | ALL |
| 846B | 24 | PW | U6 | 8-0 | 34-61-15 | D06223P | | 13 | | | | TB0145X | D047 | BJ | | 050-099, 150-199, 275-276 |
| 846B | 24 | PW | U6 | 6-0 | 34-61-15 | D06223P | | 13 | | | | TB0145X | D083 | BJ | | 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 70

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------|---------|-------|------|------|---------|---------|------|------|------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0135 | 286T0135 | | | | E2-3 L SHELF (continued) | | | | | | | | | | | |
| 846R | 24 | PW | U6 | 0-0 | 34-61-15 | D06223P | | 12 | | TB0145X | C047 | BJ | | 050-099, 150-199, 275-276 | | |
| 846R | 24 | PW | U6 | 0-0 | 34-61-15 | D06223P | | 12 | | TB0145X | C083 | BJ | | 277-299 | | |
| 846Z | | | U6 | 0-0 | 34-61-15 | D06223P | | 14 | | GDY0008 | S.. | 2 | | 050-099, 150-199, 275-276 | | |
| 846Z | | | U6 | 0-0 | 34-61-15 | D06223P | | 14 | | GDY0012 | S.. | 2 | | 277-299 | | |
| 847 | 24 | PK | | 7-0 | 34-61-15 | D06223P | | 2 | | D05733P | 26 | | | ALL | | |
| 848 | 24 | PK | | 7-0 | 34-61-15 | D06223P | | 3 | | D05733P | 27 | | | ALL | | |
| 849 | 24 | PK | | 8-0 | 34-61-15 | D06223P | | 10 | | TB0145X | B047 | BJ | | 050-099, 150-199, 275-276 | | |
| 849 | 24 | PK | | 6-0 | 34-61-15 | D06223P | | 10 | | TB0145X | B083 | BJ | | 277-278 | | |
| 849 | 24 | PK | | 8-0 | 34-61-15 | D06223P | | 10 | | TB0145X | B083 | BJ | | 280-299 | | |
| 850 | 24 | PK | | 8-0 | 34-61-15 | D06223P | | 11 | | TB0145Y | A032 | BJ | | ALL | | |
| 852 | 24 | PK | | 5-0 | 34-61-14 | D05733P | | 25 | | TB0145Y | A112 | BJ | | 050-099, 150-199, 276 | | |
| 852 | 24 | PK | | 5-0 | 34-61-14 | D05733P | | 25 | | TB0145Y | A118 | BJ | | 277-299 | | |
| 854 | 24 | PK | | 4-0 | 34-61-14 | D05225P | | 9 | | TB0145Y | A112 | BJ | | 050-099, 150-199, 276 | | |
| 854 | 24 | PK | | 4-0 | 34-61-14 | D05225P | | 9 | | TB0145Y | A118 | BJ | | 277-299 | | |
| 855 | 24 | PV | AG | 7-0 | 34-61-24 | D04725P | | 13 | | TB0145Y | A112 | BJ | | 050-099, 155-199, 276 | | |
| 855 | 24 | PV | AG | 7-0 | 34-61-24 | D04725P | | 13 | | TB0145Y | A118 | BJ | | 277-299 | | |
| 855Z | | | AG | 0-0 | 34-61-24 | D04725P | | DED | | TB0145Y | DED | | | 050-099, 155-199, 276-299 | | |
| 857B | 24 | PW | V7 | 4-0 | 34-45-12 | D05207P | | 41 | | TB0145X | A119 | BJ | | 050-099, 150-152, 155-199 | | |
| 857B | 24 | PW | V7 | 4-0 | 34-45-12 | D05207P | | 41 | | TB0145X | A124 | BJ | | 277-299 | | |
| 857R | 24 | PW | V7 | 0-0 | 34-45-12 | D05207P | | 40 | | TB0145X | A118 | BJ | | 050-099, 150-152, 155-199 | | |
| 857R | 24 | PW | V7 | 0-0 | 34-45-12 | D05207P | | 40 | | TB0145X | A123 | BJ | | 277-299 | | |
| 857Z | | | V7 | 0-0 | 34-45-12 | D05207P | | 42 | | TB0145X | REF | | V7 | 050-099, 150-152, 155-199, 277-299 | | |
| 883 | 24 | PK | | 4-0 | 34-61-27 | TB0145D | | A189 | 2 | D06199P | 7 | | | 157, 167-199, 277-278 | | |
| 883 | 24 | PK | | 6-0 | 34-61-27 | D06199P | | 7 | | TB0145D | A189 | 2 | | 275-276 | | |
| 883 | 24 | PK | | 3-0 | 34-61-27 | TB0145D | | A189 | 2 | D06199P | 7 | | | 280-299 | | |
| 891 | 24 | PK | | 3-0 | 31-31-17 | TB0145R | | A187 | 2 | TB0145R | A188 | 2 | | ALL | | |
| 892 | 24 | PK | | 5-0 | 31-31-17 | TB0145R | | A188 | 2 | TB0145Z | 138 | BJ | | ALL | | |
| FR3 | | | | 0-0 | 34-45-12 | TB0145X | | REF | | T3 | TB0145X | C119 | BJ | 050-099, 150-152, 155-199 | | |
| FR3 | | | | 0-0 | 34-45-12 | TB0145X | | REF | | V3 | TB0145X | C119 | BJ | 153-154 | | |
| FR3 | | | | 0-0 | 34-45-12 | TB0145X | | REF | | T3 | TB0145X | C124 | BJ | 277-299 | | |
| FRB | | | | 0-0 | 31-31-13 | D04729P | | | | FB | D04729P | 3 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 71

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0135 | 286T0135 | | | E2-3 L SHELF (continued) | | | | | | | | | | | | | |
| FRE | | | | 0-0 | 34-61-14 | D05705J | | 18 | | | | | D05705J | | | KA | ALL |
| FRF | | | | 0-0 | 34-61-14 | D05733P | REF | | | LA | | | D05733P | 31 | | | 050-099, 150-156, 162-166 |
| FRL | | | | 0-0 | 34-45-12 | GDY0003 | S.. | 2 | | | | | TB0145X | REF | | V7 | 050-099, 277-299 |
| FRL | | | | 0-0 | 34-45-12 | GDY0002 | S.. | 2 | | | | | TB0145X | REF | | V7 | 150-152 |
| FRL | | | | 0-0 | 34-45-12 | TB0145X | REF | | | LX | | | GDY0003 | S.. | 2 | | 153-154 |
| FRL | | | | 0-0 | 34-45-12 | TB0145X | REF | | | V7 | | | GDY0003 | S.. | 2 | | 155-199 |
| FRV | | | | 0-0 | 34-45-12 | GDY0003 | S.. | 2 | | | | | TB0145X | REF | | T3 | 050-099, 277-299 |
| FRV | | | | 0-0 | 34-45-12 | GDY0002 | S.. | 2 | | | | | TB0145X | REF | | T3 | 150-152 |
| FRV | | | | 0-0 | 34-45-12 | TB0145X | REF | | | V3 | | | GDY0003 | S.. | 2 | | 153-154 |
| FRV | | | | 0-0 | 34-45-12 | TB0145X | REF | | | T3 | | | GDY0003 | S.. | 2 | | 155-199 |
| FRX | | | | 0-0 | 34-45-12 | TB0145X | REF | | | V7 | | | TB0145X | C118 | BJ | | 050-099, 150-152, 155-199 |
| FRX | | | | 0-0 | 34-45-12 | TB0145X | REF | | | LX | | | TB0145X | C118 | BJ | | 153-154 |
| FRX | | | | 0-0 | 34-45-12 | TB0145X | REF | | | V7 | | | TB0145X | C123 | BJ | | 277-299 |
| W0136 | 286T0136 | | | P33-THRUST REVERSER MODIF. ASSY-R2 | | | | | | | | | | | | | |
| 015 | 20 | PQ | AO | 3-0 | 78-34-21 | D20178 | | B2 | | | | | TB0460Y | C005 | BJ | | ALL |
| 015Z | | | AO | 0-0 | 78-34-21 | D20178 | | DED | | | | | TB0460Y | DED | | | ALL |
| 016 | 20 | PQ | AP | 2-0 | 78-34-21 | D20178 | | A1 | | | | | D20190 | C1 | | | ALL |
| 016Z | | | AP | 0-0 | 78-34-21 | D20178 | | | | AE | | | D20190 | DED | | | ALL |
| 018 | 20 | PA | | 3-0 | 78-34-21 | D20178 | | C1 | | | | | TB0460X | C001 | BJ | | ALL |
| 019 | 20 | PQ | AS | 3-0 | 78-34-21 | D20178 | | X1 | | | | | TB0460Y | C005 | BJ | | ALL |
| 019Z | | | AS | 0-0 | 78-34-21 | D20178 | | DED | | | | | TB0460Y | DED | | | ALL |
| 020 | 20 | PA | | 3-0 | 78-34-21 | D20178 | | X2 | | | | | GDY0013 | D.. | 2 | | ALL |
| 024 | 20 | PQ | AX | 3-0 | 78-34-21 | D20178 | | A2 | | | | | TB0460Y | C005 | BJ | | ALL |
| 024Z | | | AX | 0-0 | 78-34-21 | D20178 | | DED | | | | | TB0460Y | DED | | | ALL |
| 026 | 20 | PQ | BA | 3-0 | 78-34-21 | D20190 | | A1 | | | | | TB0460Z | 8 | BJ | | ALL |
| 026Z | | | BA | 0-0 | 78-34-21 | D20190 | | DED | | | | | TB0460Z | | | AB | ALL |
| 027 | 20 | PQ | BB | 3-0 | 78-34-21 | D20190 | | B1 | | | | | TB0460Z | 8 | BJ | | ALL |
| 027Z | | | BB | 0-0 | 78-34-21 | D20190 | | DED | | | | | TB0460Z | | | AB | ALL |
| 040 | 20 | PQ | BO | 3-0 | 78-34-21 | D20186 | | A2 | | | | | TB0460X | A001 | BJ | | ALL |
| 040Z | | | BO | 0-0 | 78-34-21 | D20186 | | | | AG | | | TB0460X | C002 | BJ | | ALL |
| 041 | 20 | PA | | 3-0 | 78-34-21 | D20186 | | A3 | | | | | GDY0015 | D.. | 2 | | ALL |
| 042 | 20 | PA | | 3-0 | 78-34-21 | D20186 | | A1 | | | | | TB0460X | B001 | BJ | | ALL |
| 043 | 20 | PQ | BR | 3-0 | 78-34-21 | D20186 | | X1 | | | | | TB0460Z | 8 | BJ | | ALL |
| 043Z | | | BR | 0-0 | 78-34-21 | D20186 | | DED | | | | | TB0460Z | | | AB | ALL |
| 044 | 20 | PA | | 3-0 | 78-34-21 | D20186 | | X2 | | | | | GDY0015 | D.. | 2 | | ALL |
| 045 | 20 | PQ | BT | 3-0 | 78-34-21 | D20190 | | X1 | | | | | TB0460Z | 8 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 72

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|----|-----|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0136 | 286T0136 | | | P33-THRUST REVERSER MODIF. ASSY-R2 (continued) | | | | | | | | | | | | | | | |
| 045Z | | | | BT | 0-0 | 78-34-21 | D20190 | | DED | | | | | | TB0460Z | | | AB | ALL |
| 046 | 20 | PA | | | 3-0 | 78-34-21 | D20190 | | A3 | | | | | | GDY0013 | D.. | 2 | | ALL |
| 047 | 20 | PA | | | 3-0 | 78-34-21 | D20190 | | B3 | | | | | | GDY0013 | D.. | 2 | | ALL |
| 048 | 20 | PA | | | 3-0 | 78-34-21 | D20190 | | X2 | | | | | | GDY0013 | D.. | 2 | | ALL |
| 049 | 20 | PA | | | 1-0 | 78-34-21 | TB0460Y | | A006 | BJ | | | | | TB0460D | C003 | 2 | | ALL |
| 050 | 20 | PQ | | BY | 3-0 | 78-34-21 | D20190 | | A2 | | | | | | TB0460Y | A006 | BJ | | ALL |
| 050Z | | | | BY | 0-0 | 78-34-21 | D20190 | | DED | | | | | | TB0460Y | | | AC | ALL |
| 051 | 20 | PA | | | 3-0 | 78-34-21 | TB0460Y | | | | AC | | | | GDY0015 | S.. | 2 | | ALL |
| 052 | 20 | PQ | | CB | 3-0 | 78-34-21 | D20190 | | B2 | | | | | | TB0460Y | C006 | BJ | | ALL |
| 052Z | | | | CB | 0-0 | 78-34-21 | D20190 | | DED | | | | | | TB0460Y | | | AC | ALL |
| 053 | 20 | PA | | | 1-0 | 78-34-21 | TB0460Y | | C006 | BJ | | | | | TB0460D | C004 | 2 | | ALL |
| 054 | 20 | PA | | | 3-0 | 78-34-21 | TB0460D | | A004 | 2 | | | | | GDY0015 | D.. | 2 | | ALL |
| 055 | 20 | PA | | | 3-0 | 78-34-21 | TB0460D | | A003 | 2 | | | | | GDY0015 | D.. | 2 | | ALL |
| 063 | 20 | PA | | | 1-0 | 78-34-21 | D20190 | | D2 | | | | | | D20190 | Y1 | | | ALL |
| 064 | 20 | PA | | | 3-0 | 78-34-21 | D20190 | | Y2 | | | | | | M01991 | A | C | | ALL |
| 065 | 20 | PA | | | 3-0 | 78-34-21 | M01991 | | B | C | | | | | GDY0013 | D.. | 2 | | ALL |
| 066 | 20 | PQ | | CP | 2-0 | 78-34-21 | D20178 | | B3 | | | | | | D20186 | B2 | | | ALL |
| 066Z | | | | CP | 0-0 | 78-34-21 | D20178 | | | | AE | | | | D20186 | DED | | | ALL |
| 067 | 20 | PA | | | 3-0 | 78-34-21 | D20190 | | D3 | | | | | | GDY0013 | D.. | 2 | | ALL |
| 068 | 20 | PQ | | CR | 2-0 | 78-34-21 | D20186 | | B3 | | | | | | D20190 | D1 | | | ALL |
| 068Z | | | | CR | 0-0 | 78-34-21 | D20186 | | | | AA | | | | D20190 | DED | | | ALL |
| 070 | 20 | PQ | | CT | 3-0 | 78-34-21 | D20190 | | C2 | | | | | | TB0460Z | 8 | BJ | | ALL |
| 070Z | | | | CT | 0-0 | 78-34-21 | D20190 | | DED | | | | | | TB0460Z | | | AB | ALL |
| 071 | 20 | PA | | | 3-0 | 78-34-21 | D20178 | | | | AE | | | | GDY0013 | S.. | 2 | | ALL |
| 073 | 20 | PA | | | 3-0 | 78-34-21 | GDY0015 | | S.. | 2 | | | | | TB0460Z | | | AB | ALL |
| 074 | 20 | PA | | | 3-0 | 78-34-21 | D20186 | | | | AA | | | | GDY0015 | S.. | 2 | | ALL |
| 075 | 24 | PK | | | 3-0 | 78-36-21 | TB0460D | | C013 | 2 | | | | | D20112 | 2 | | | ALL |
| 076 | 24 | PK | | | 3-0 | 78-36-21 | TB0460X | | A009 | BJ | | | | | D20112 | 5 | | | ALL |
| 077 | 24 | PK | | | 3-0 | 78-36-21 | TB0460X | | B009 | BJ | | | | | D20112 | 8 | | | ALL |
| 078 | 24 | PK | | | 3-0 | 78-36-21 | TB0460X | | C009 | BJ | | | | | D20112 | 6 | | | ALL |
| 079 | 24 | PK | | | 3-0 | 78-36-21 | TB0460D | | C014 | 2 | | | | | D20112 | 3 | | | ALL |
| 080 | 24 | PK | | | 3-0 | 78-36-21 | TB0460X | | A010 | BJ | | | | | D20112 | 1 | | | ALL |
| 081 | 24 | PK | | | 3-0 | 78-36-21 | TB0460Z | | 7 | BJ | | | | | D20112 | 7 | | | ALL |
| 082 | 20 | PA | | | 3-0 | 78-34-21 | D20186 | | | | AG | | | | GDY0015 | S.. | 2 | | ALL |
| W0138 | 286T0138 | | | P33-R1-POWER DISTRIBUTION | | | | | | | | | | | | | | | |
| 001 | 08 | HA | | | 6-0 | 24-51-52 | D04330J | | A | | | | | | TB5096 | 10 | N | | ALL |
| 002 | 08 | HA | | | 6-0 | 24-51-52 | D04330J | | B | | | | | | TB5096 | 11 | N | | ALL |
| 003 | 08 | HA | | | 6-0 | 24-51-52 | D04330J | | C | | | | | | TB5096 | 12 | N | | ALL |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0138 | 286T0138 | | | P33-R1-POWER DISTRIBUTION (continued) | | | | | | | | | | | | |
| 004 | 10 | | HA | 4-0 | 24-51-52 | TB5096 | 10 | N2 | *1 | C00333 | A1 | M | * | ALL | | |
| 005 | 10 | | HA | 5-0 | 24-51-52 | TB5096 | 10 | N2 | *1 | C00321 | A1 | M | * | ALL | | |
| 006 | 12 | | HA | 2-0 | 24-51-52 | C00333 | A1 | M | * | C00301 | A2 | M | * | ALL | | |
| 007 | 12 | | HA | 2-0 | 24-51-52 | C00301 | A2 | M | * | C00302 | A2 | M | * | ALL | | |
| 008 | 12 | | HA | 2-0 | 24-51-52 | C00302 | A2 | M | * | C00870 | 1 | M | * | ALL | | |
| 009 | 12 | | HA | 3-0 | 24-51-52 | C00870 | 1 | M | * | C00363 | A1 | M | * | ALL | | |
| 010 | 12 | | HA | 3-0 | 24-51-52 | C00363 | A1 | M | * | C00397 | A1 | M | * | ALL | | |
| 011 | 12 | | HA | 3-0 | 24-51-52 | C00397 | B1 | M | * | C00363 | B1 | M | * | 050-099 | | |
| 011 | 12 | | HA | 3-0 | 24-51-52 | C00363 | B1 | M | * | C00397 | B1 | M | * | 150-199, 275-299 | | |
| 012 | 12 | | HA | 3-0 | 24-51-52 | C00363 | C1 | M | * | C00397 | C1 | M | * | ALL | | |
| 014 | 12 | | HA | 3-0 | 24-51-52 | C01279 | 2 | M | * | C01266 | 1 | M | * | 050-099, 165 | | |
| 014 | 12 | | HA | 3-0 | 24-51-52 | C01279 | 2 | D | * | C01266 | 1 | M | * | 150-154, 162-164 | | |
| 014 | 12 | | HA | 4-0 | 24-51-52 | C01279 | 2 | M | * | C01266 | 1 | M | * | 155-157, 166-199, 275-299 | | |
| 015 | 12 | | HA | 2-0 | 24-51-52 | C01266 | 1 | M | * | C01255 | 1 | M | * | 050-099, 150-154, 162-165, 275-276, 280-299 | | |
| 015 | 12 | | HA | 3-0 | 24-51-52 | C01266 | 1 | M | * | C01255 | 1 | M | * | 155-157, 166-199 | | |
| 015 | 12 | | HA | 1-0 | 24-51-52 | C01266 | 1 | M | * | C01255 | 1 | M | * | 277-278 | | |
| 018 | 10 | | HA | 4-0 | 24-51-52 | TB5096 | 11 | N2 | *1 | C00333 | B1 | M | * | ALL | | |
| 019 | 10 | | HA | 5-0 | 24-51-52 | TB5096 | 11 | N2 | *1 | C00321 | B1 | M | * | ALL | | |
| 020 | 12 | | HA | 2-0 | 24-51-52 | C00333 | B1 | M | * | C00301 | B2 | M | * | 050-099, 150-155, 162-165, 275-276 | | |
| 020 | 12 | | HA | 2-0 | 24-51-52 | C00676 | 1 | M | * | C00301 | B2 | M | * | 156-157, 166-199, 277-299 | | |
| 021 | 12 | | HA | 2-0 | 24-51-52 | C00301 | B2 | M | * | C00302 | B2 | M | * | ALL | | |
| 022 | 12 | | HA | 3-0 | 24-51-52 | C00302 | B2 | M | * | C00363 | B1 | M | * | ALL | | |
| 027 | 10 | | HA | 5-0 | 24-51-52 | C00871 | 1 | M | * | TB5096 | 12 | N2 | *2 | 050-099, 155-199 | | |
| 027 | 10 | | HA | 6-0 | 24-51-52 | C00871 | 1 | M | * | TB5096 | 12 | N2 | *2 | 150-154, 275-299 | | |
| 028 | 12 | | HA | 3-0 | 24-51-52 | C00397 | B1 | M | * | C01263 | 1 | M | * | 050-099, 155-199, 276-299 | | |
| 028 | 12 | | HA | 3-0 | 24-51-52 | C00397 | B1 | M | * | C01263 | 1 | M | * | 150-154, 275 | | |
| 030 | 10 | | HA | 2-0 | 24-51-52 | C01222 | 2 | M | * | C01262 | 2 | M | * | 050-099 | | |
| 030 | 12 | | HA | 2-0 | 24-51-52 | C01263 | 1 | M | * | C01262 | 2 | M | * | 150-154, 275 | | |
| 030 | 12 | | HA | 2-0 | 24-51-52 | C01222 | 2 | M | * | C01262 | 2 | M | * | 155-199 | | |
| 030 | 12 | | HA | 2-0 | 24-51-52 | C01222 | 2 | M | * | C01262 | 2 | M | * | 276-299 | | |
| 031 | 10 | | HA | 4-0 | 24-51-52 | TB5096 | 12 | N2 | *1 | C00333 | C1 | M | * | ALL | | |
| 032 | 10 | | HA | 5-0 | 24-51-52 | TB5096 | 12 | N2 | *1 | C00321 | C1 | M | * | ALL | | |
| 033 | 12 | | HA | 3-0 | 24-51-52 | C00333 | C1 | M | * | C00301 | C2 | M | * | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 74

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|--------|------|------|--------|-------|---------|------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0138 | 286T0138 | | | P33-R1-POWER DISTRIBUTION (continued) | | | | | | | | | | | | |
| 034 | 12 | | HA | | 2-0 | 24-51-52 | C00301 | | C2 | M | * | C00302 | C2 | M | * | ALL |
| 035 | 12 | | HA | | 3-0 | 24-51-52 | C00302 | | C2 | M | * | C00363 | C1 | M | * | ALL |
| 039 | 12 | | HA | | 2-0 | 24-51-52 | C00397 | | C1 | M | * | C01206 | 2 | M | * | 050-099 |
| 039 | 12 | | HA | | 3-0 | 24-51-52 | C01206 | | 2 | M | * | C00397 | C1 | M | * | 150-162, 166-199, 275-276 |
| 039 | 12 | | HA | | 2-0 | 24-51-52 | C01206 | | 2 | M | * | C00397 | C1 | M | * | 163-165, 280-299 |
| 039 | 12 | | HA | | 1-0 | 24-51-52 | C01206 | | 2 | M | * | C00397 | C1 | M | * | 277-278 |
| 040 | 12 | | HA | | 3-0 | 24-51-52 | C01206 | | 2 | M | * | C01265 | 1 | M | * | ALL |
| 041 | 12 | | HA | | 2-0 | 24-51-52 | C00731 | | 1 | M | * | C01474 | 1 | M | * | 050-099, 277-299 |
| 041 | 12 | | HA | | 2-0 | 24-51-52 | C00731 | | 1 | M | * | C01474 | 1 | M | * | 150-199 |
| 042 | 12 | | HA | | 2-0 | 24-51-52 | C00871 | | 1 | M | * | C01474 | 1 | M | * | 050-099, 277-299 |
| 042 | 12 | | HA | | 2-0 | 24-51-52 | C00871 | | 1 | M | * | C01474 | 1 | M | * | 150-199, 275-276 |
| 046 | 12 | | HA | | 7-0 | 24-53-51 | T00126 | | HV | N | * | C00871 | 2 | M | * | ALL |
| 047 | 10 | | HA | | 2-0 | 24-53-51 | C01258 | | 1 | M | * | C01205 | 2 | M | * | ALL |
| 048 | 10 | | HA | | 3-0 | 24-53-51 | T00126 | | GND | N | * | GDX0009 | A.. | F | * | 050-099, 150-154, 162-164, 275-276 |
| 048 | 10 | | HA | | 3-0 | 24-53-51 | T00126 | | GND | N | * | GDX0009 | A.. | P | * | 155-157, 165-199, 277-299 |
| 049 | 10 | | HA | | 6-0 | 24-53-51 | T00126 | | LV | N | * | C01165 | 2 | M | * | ALL |
| 068 | 10 | | HA | | 3-0 | 24-51-52 | C00536 | | 2 | D | * | C01149 | 1 | D | * | 050-099 |
| 068 | 12 | | HA | | 4-0 | 24-51-52 | C01149 | | 1 | M | * | C00536 | 2 | M | * | 150-199, 276-299 |
| 068 | 12 | | HA | | 4-0 | 24-51-52 | C01207 | | 2 | M | * | C00536 | 2 | M | * | 275 |
| 070 | 10 | | HA | | 6-0 | 24-51-52 | TB5096 | | 10 | N2 | *2 | C01279 | 2 | M | * | 050-099 |
| 070 | 12 | | PA | | 6-0 | 24-51-52 | C01279 | | 2 | D | * | TB5096 | 10 | N1 | *2 | 150-154, 162-164 |
| 070 | 12 | | HA | | 6-0 | 24-51-52 | C01279 | | 2 | M | * | TB5096 | 10 | N1 | *2 | 155-157, 165-199 |
| 070 | 10 | | HA | | 6-0 | 24-51-52 | C01279 | | 2 | M | * | TB5096 | 10 | N2 | *2 | 275-299 |
| 073 | 10 | | HA | | 3-0 | 24-51-52 | TB5096 | | 10 | N2 | *2 | K00622 | A2 | N | * | 050-099, 275-299 |
| 073 | 10 | | HA | | 3-0 | 24-51-52 | TB5096 | | 10 | N1 | *2 | K00622 | A2 | N | * | 150-199 |
| 074 | 10 | | HA | | 3-0 | 24-51-52 | TB5096 | | 11 | N1 | *2 | K00622 | B2 | N | * | ALL |
| 075 | 10 | | HA | | 3-0 | 24-51-52 | TB5096 | | 12 | N2 | *2 | K00622 | C2 | N | * | ALL |
| 078 | 10 | | HA | | 6-0 | 24-51-52 | C01142 | | 2 | M | * | K00622 | C3 | N | * | ALL |
| 079 | 10 | | HA | | 2-0 | 24-51-52 | C01207 | | 2 | M | * | C01219 | 2 | M | * | 050-099 |
| 079 | 12 | | HA | | 2-0 | 24-51-52 | C01207 | | 2 | M | * | C01219 | 2 | M | * | 150-199, 275-299 |
| 081 | 10 | | HA | | 3-0 | 24-51-52 | C01207 | | 2 | D | * | C01149 | 1 | D | * | 050-099 |
| 081 | 12 | | HA | | 3-0 | 24-51-52 | C01149 | | 1 | M | * | C01207 | 2 | M | * | 150-199, 276-299 |
| 082 | 10 | | HA | | 7-0 | 24-51-52 | C00531 | | 2 | M | * | K00622 | A3 | N | * | 050-099 |
| 082 | 10 | | HA | | 6-0 | 24-51-52 | C00531 | | 2 | M | * | K00622 | A3 | N | * | 150-199, 275-299 |
| 083 | 10 | | HA | | 3-0 | 24-51-52 | C01158 | | 2 | M | * | C01262 | 2 | M | * | 050-099 |
| 083 | 12 | | HA | | 3-0 | 24-51-52 | C01158 | | 2 | M | * | C01222 | 2 | M | * | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 75

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0138 | 286T0138 | | | P33-R1-POWER DISTRIBUTION (continued) | | | | | | | | | | | | |
| 083 | 12 | | HA | 3-0 | 24-51-52 | C01158 | | 2 | M | * | C01262 | 2 | M | * | 276-299 | |
| 084 | 10 | | HA | 7-0 | 24-51-52 | C01222 | | 2 | M | * | K00622 | B3 | N | | 050-099, 150-154 | |
| 084 | 10 | | HA | 7-0 | 24-51-52 | C01262 | | 2 | M | * | K00622 | B3 | N | | 155-199 | |
| 084 | 10 | | HA | 7-0 | 24-51-52 | C01222 | | 2 | M | | K00622 | B3 | N | | 275 | |
| 084 | 10 | | HA | 7-0 | 24-51-52 | C01158 | | 2 | M | * | K00622 | B3 | N | | 276-299 | |
| 085 | 12 | | HA | 3-0 | 24-51-52 | C01150 | | 2 | D | * | C01211 | 2 | D | | 050-099 | |
| 085 | 12 | | HA | 3-0 | 24-51-52 | C01150 | | 2 | M | * | C01211 | 2 | M | | 150-199, 276-299 | |
| 086 | 10 | | HA | 1-0 | 24-51-52 | C01142 | | 2 | M | * | C00536 | 2 | M | * | 050-099 | |
| 086 | 12 | | HA | 2-0 | 24-51-52 | C01142 | | 2 | M | * | C00536 | 2 | M | * | 150-199, 275-299 | |
| 098 | 14 | | HA | 3-0 | 24-53-51 | C01205 | | 2 | M | * | C01229 | 1 | M | * | 050-099 | |
| 098 | 10 | | HA | 2-0 | 24-53-51 | C01205 | | 2 | M | * | C01229 | 1 | M | * | 150-199, 275-299 | |
| 099 | 14 | | HA | 3-0 | 24-53-51 | C01229 | | 1 | M | * | C01213 | 1 | M | * | 050-099 | |
| 099 | 10 | | HA | 3-0 | 24-53-51 | C01229 | | 1 | M | * | C01213 | 1 | M | * | 150-199, 275-299 | |
| 100 | 14 | | HA | 2-0 | 24-53-51 | C01213 | | 1 | M | * | C01269 | 1 | M | | 050-099 | |
| 100 | 10 | | HA | 2-0 | 24-53-51 | C01213 | | 1 | M | * | C01269 | 1 | M | | 150-199, 275-299 | |
| 101 | 14 | | HA | 4-0 | 24-51-52 | TB5096 | | 11 | N1 | *2 | L00575 | 1 | L | | ALL | |
| 102 | 14 | | HA | 4-0 | 24-51-52 | L00575 | | 2 | L | | GDX0009 | A.. | P | | ALL | |
| 105 | 10 | | HA | 3-0 | 24-53-51 | C01165 | | 2 | M | * | C01258 | 1 | M | * | 050-099 | |
| 105 | 10 | | HA | 4-0 | 24-53-51 | C01258 | | 1 | M | * | C01165 | 2 | M | * | 150-199, 275-299 | |
| 106 | 12 | | HA | 7-0 | 24-51-24 | C01220 | | 2 | D | * | D06476J | 1 | | | 050-099 | |
| 106 | 12 | | HA | 8-0 | 24-51-24 | C01220 | | 2 | M | * | D06476J | 1 | | | 150-199, 275-299 | |
| 107 | 12 | | HA | 2-0 | 24-51-24 | C01220 | | 2 | D | * | C01221 | 2 | D | | 050-099 | |
| 107 | 12 | | HA | 2-0 | 24-51-24 | C01220 | | 2 | M | * | C01221 | 2 | M | | 150-199, 275-299 | |
| 109 | 10 | | HA | 3-0 | 24-51-52 | C00531 | | 2 | M | * | C01150 | 2 | M | * | 050-099 | |
| 109 | 10 | | HA | 4-0 | 24-51-52 | C00531 | | 2 | M | * | C01150 | 2 | M | * | 150-199, 276-299 | |
| 109 | 10 | | HA | 4-0 | 24-51-52 | C00531 | | 2 | M | * | C01211 | 2 | M | | 275 | |
| 700 | 12 | | HA | 2-0 | 24-51-52 | C00333 | | B1 | M | * | C00676 | 1 | M | * | 156-157, 166-199, 277-299 | |
| W0139 | 286T0139 | | | E2-5 SHELF,L | | | | | | | | | | | | |
| 001 | 16 | | PA | 6-0 | 23-12-11 | D00439C | | 2 | | | TB0139G | 123 | 2 | | 050-099, 150-157, 275-277 | |
| 001 | 16 | | PA | 6-0 | 23-12-11 | D00439C | | 2 | | | TB0139G | 40 | 2 | | 162-199 | |
| 001 | 16 | | PA | 5-0 | 23-12-11 | D00439C | | 2 | | | TB0139G | 123 | 2 | | 278-299 | |
| 002 | 18 | | PA | 5-0 | 23-12-11 | D04927P | | 4 | | | TB0139G | 123 | 2 | | 050-099, 150-157, 275-277 | |
| 002 | 18 | | PA | 5-0 | 23-12-11 | D04927P | | 4 | | | TB0139G | 40 | 2 | | 162-199 | |
| 002 | 18 | | PA | 3-7 | 23-12-11 | D04927P | | 4 | | | TB0139G | 123 | 2 | | 278-299 | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 76

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 005 | 16 | | PA | | 3-0 | 23-12-11 | D00439C | | 4 | | GDX0013 | D.. | 2 | | 050-099, 150-199, 275-277 |
| 005 | 16 | | PA | | 2-2 | 23-12-11 | D00439C | | 4 | | GDX0013 | D.. | 2 | | 278-299 |
| 006 | 22 | | PA | | 3-0 | 23-12-11 | D00439B | | D03 | | GDX0013 | D.. | 2 | | 050-099, 150-199, 275-277 |
| 006 | 22 | | PA | | 2-2 | 23-12-11 | D00439B | | D03 | | GDX0013 | D.. | 2 | | 278-299 |
| 007 | 16 | | PA | | 3-0 | 23-12-21 | D00443C | | 2 | | TB0139G | 183 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 007 | 16 | | PA | | 4-0 | 23-12-21 | D00443C | | 2 | | TB0139G | 171 | 2 | | 157, 167-199, 277 |
| 007 | 16 | | PA | | 3-2 | 23-12-21 | D00443C | | 2 | | TB0139G | 171 | 2 | | 278-299 |
| 008 | 18 | | PA | | 5-0 | 23-12-21 | D04929P | | 4 | | TB0139G | 183 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 008 | 18 | | PA | | 4-0 | 23-12-21 | D04929P | | 4 | | TB0139G | 171 | 2 | | 157, 167-199 |
| 008 | 18 | | PA | | 5-0 | 23-12-21 | D04929P | | 4 | | TB0139G | 171 | 2 | | 277 |
| 008 | 18 | | PA | | 3-6 | 23-12-21 | D04929P | | 4 | | TB0139G | 171 | 2 | | 278-299 |
| 012 | 24 | | PK | | 4-0 | 23-22-12 | D00447A | | J05 | | D04931P | 12 | | | 167-199 |
| 012 | 22 | | PA | | 5-0 | 23-22-12 | D04953P | | 22 | | D00447A | J05 | | | 275-276 |
| 012 | 22 | | PA | | 5-0 | 23-22-12 | D04957P | | 53 | | D00447A | J05 | | | 277 |
| 012 | 22 | | PA | | 4-2 | 23-22-12 | D04957P | | 53 | | D00447A | J05 | | | 278 |
| 012 | 22 | | PA | | 10-0 | 23-22-12 | D04953P | | 22 | | D00447A | J05 | | | 280-299 |
| 013 | 16 | | PA | | 3-0 | 23-12-21 | D00443C | | 4 | | GDX0011 | D.. | 2 | | 050-099, 150-199, 275-277 |
| 013 | 16 | | PA | | 2-5 | 23-12-21 | D00443C | | 4 | | GDX0011 | D.. | 2 | | 278-299 |
| 014 | 22 | | PA | | 3-0 | 23-12-21 | D00443B | | D03 | | GDX0011 | D.. | 2 | | 050-099, 150-199, 275-277 |
| 014 | 22 | | PA | | 2-5 | 23-12-21 | D00443B | | D03 | | GDX0011 | D.. | 2 | | 278-299 |
| 015 | 20 | | PA | | 6-0 | 23-21-11 | D00441C | | 2 | | D04213P | 2 | | | 050-099, 150-199, 275-277 |
| 015 | 20 | | PA | | 6-1 | 23-21-11 | D00441C | | 2 | | D04213P | 2 | | | 278-299 |
| 016 | 20 | | PA | | 3-0 | 23-21-11 | D00441C | | 3 | | GDX0013 | D.. | 2 | | 050-099, 150-199, 275-277 |
| 016 | 20 | | PA | | 2-1 | 23-21-11 | D00441C | | 3 | | GDX0013 | D.. | 2 | | 278-299 |
| 017 | 20 | | PA | | 3-0 | 23-21-11 | D00441C | | 4 | | GDX0013 | S.. | 2 | | 050-099, 150-199, 275-277 |
| 017 | 20 | | PA | | 2-1 | 23-21-11 | D00441C | | 4 | | GDX0013 | S.. | 2 | | 278-299 |
| 018 | 24 | | PK | | 6-0 | 23-21-11 | D05001P | | 21 | | TB0139G | 178 | 2 | | 050-099 |
| 018 | 24 | | PK | | 4-0 | 23-21-11 | D05001P | | 21 | | TB0139G | 178 | 2 | | 150-156, 162-166, 275-276 |
| 018 | 24 | | PK | | 4-0 | 23-21-11 | D05001P | | 21 | | TB0139Y | A177 | BJ | | 157, 167-199, 277 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 77

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 018 | 24 | | PK | 2-11 | 23-21-11 | D05001P | | 21 | | | TB0139Y | A177 | BJ | | 278-299 | |
| 019 | 24 | | PK | 6-0 | 23-21-11 | D05001P | | 22 | | | TB0139G | 179 | 2 | | 050-099 | |
| 019 | 24 | | PK | 4-0 | 23-21-11 | D05001P | | 22 | | | TB0139G | 179 | 2 | | 150-156, 162-166, 275-276 | |
| 019 | 24 | | PK | 4-0 | 23-21-11 | D05001P | | 22 | | | TB0139Y | C177 | BJ | | 157, 167-199, 277 | |
| 019 | 24 | | PK | 2-11 | 23-21-11 | D05001P | | 22 | | | TB0139Y | C177 | BJ | | 278-299 | |
| 020 | 24 | | PK | 3-0 | 23-21-11 | D05001P | | 26 | | | D00441B | A01 | | | 050-099, 150-199, 275-277 | |
| 020 | 24 | | PK | 2-8 | 23-21-11 | D05001P | | 26 | | | D00441B | A01 | | | 278-299 | |
| 021 | 24 | | PK | 3-0 | 23-21-11 | D05001P | | 27 | | | D00441B | B01 | | | 050-099, 150-199, 275-277 | |
| 021 | 24 | | PK | 2-8 | 23-21-11 | D05001P | | 27 | | | D00441B | B01 | | | 278-299 | |
| 022 | 24 | | PK | 3-0 | 23-21-11 | D05001P | | 16 | | | D00441B | D06 | | | 050-099, 150-199, 275-277 | |
| 022 | 24 | | PK | 2-8 | 23-21-11 | D05001P | | 16 | | | D00441B | D06 | | | 278-299 | |
| 023 | 24 | | PK | 3-0 | 23-21-11 | D05001P | | 17 | | | D00441B | A07 | | | 050-099, 150-199, 275-277 | |
| 023 | 24 | | PK | 2-8 | 23-21-11 | D05001P | | 17 | | | D00441B | A07 | | | 278-299 | |
| 024 | 22 | | PA | 3-0 | 23-21-11 | D00441B | | A08 | | | GDX0013 | D.. | 2 | | 050-099, 150-199, 275-277 | |
| 024 | 22 | | PA | 2-1 | 23-21-11 | D00441B | | A08 | | | GDX0013 | D.. | 2 | | 278-299 | |
| 025 | 22 | | PA | 3-0 | 23-21-11 | D00441B | | A04 | | | GDX0013 | D.. | 2 | | 050-099, 150-199, 275-277 | |
| 025 | 22 | | PA | 2-1 | 23-21-11 | D00441B | | A04 | | | GDX0013 | D.. | 2 | | 278-299 | |
| 026 | 24 | | PK | 4-0 | 23-21-11 | D00441B | | B04 | | | TB0139D | A168 | 2 | | 050-099, 151, 275-276 | |
| 026 | 24 | | PK | 4-0 | 23-21-11 | D00441B | | B04 | | | TB0139G | 169 | 2 | | 150, 152-199, 277 | |
| 026 | 24 | | PK | 3-4 | 23-21-11 | D00441B | | B04 | | | TB0139G | 169 | 2 | | 278-299 | |
| 027 | 24 | | PK | 3-0 | 23-21-11 | D00441B | | B07 | | | D05001P | 18 | | | 050-099, 150-199, 275-277 | |
| 027 | 24 | | PK | 2-8 | 23-21-11 | D00441B | | B07 | | | D05001P | 18 | | | 278-299 | |
| 028 | 24 | | PK | 3-0 | 23-21-11 | D00441B | | C07 | | | D05001P | 19 | | | 050-099, 150-199, 275-277 | |
| 028 | 24 | | PK | 2-8 | 23-21-11 | D00441B | | C07 | | | D05001P | 19 | | | 278-299 | |
| 029 | 24 | | PK | 3-0 | 23-21-11 | D00441B | | D07 | | | D05001P | 20 | | | 050-099, 150-199, 275-277 | |
| 029 | 24 | | PK | 2-8 | 23-21-11 | D00441B | | D07 | | | D05001P | 20 | | | 278-299 | |
| 030 | 24 | | PK | 4-0 | 23-21-11 | D05001P | | 24 | | | TB0139G | 181 | 2 | | 050-099, 150-156, 162-166, 275-276 | |
| 030 | 24 | | PK | 4-0 | 23-21-11 | D05001P | | 24 | | | TB0139Y | C178 | BJ | | 157, 167-199, 277 | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 78

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 030 | 24 | | PK | | 2-11 | 23-21-11 | D05001P | 24 | | | TB0139Y | C178 | BJ | | 278-299 |
| 031 | 24 | | PK | | 4-0 | 23-21-11 | D05001P | 25 | | | TB0139G | 182 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 031 | 24 | | PK | | 4-0 | 23-21-11 | D05001P | 25 | | | TB0139Y | A184 | BJ | | 157, 167-199, 277 |
| 031 | 24 | | PK | | 2-11 | 23-21-11 | D05001P | 25 | | | TB0139Y | A184 | BJ | | 278-299 |
| 032 | 24 | | PK | | 6-0 | 23-21-11 | D05001P | 28 | | | TB0139G | 167 | 2 | | 050-099 |
| 032 | 24 | | PK | | 3-0 | 23-21-11 | TB0139G | 167 | 2 | | D05001P | 28 | | | 150, 152-154 |
| 032 | 24 | | PK | | 3-0 | 23-21-11 | D00441B | C01 | | | D05001P | 28 | | | 151, 275-276 |
| 032 | 24 | | PK | | 4-0 | 23-21-11 | TB0139G | 167 | 2 | | D05001P | 28 | | | 155-199, 277 |
| 032 | 24 | | PK | | 3-5 | 23-21-11 | TB0139G | 167 | 2 | | D05001P | 28 | | | 278-299 |
| 033 | 24 | | PK | | 3-0 | 23-21-11 | D00441B | D01 | | | D05001P | 29 | | | 050-099, 150-199, 275-277 |
| 033 | 24 | | PK | | 2-8 | 23-21-11 | D00441B | D01 | | | D05001P | 29 | | | 278-299 |
| 034 | 24 | | PK | | 3-0 | 23-21-11 | D00441B | A02 | | | D05001P | 30 | | | 050-099, 150-199, 275-277 |
| 034 | 24 | | PK | | 2-8 | 23-21-11 | D00441B | A02 | | | D05001P | 30 | | | 278-299 |
| 035 | 24 | | PK | | 4-0 | 23-51-14 | TB0139T | A172 | 2 | | TB0139H | 81 | 2 | | 050-099, 150-199, 275-277 |
| 035 | 24 | | PK | | 3-0 | 23-51-14 | TB0139T | A172 | 2 | | TB0139H | 81 | 2 | | 278-299 |
| 036 | 20 | | PA | | 3-0 | 23-51-14 | TB0139T | C172 | 2 | | GDX0011 | S.. | 2 | | 050-099, 150-199, 275-277 |
| 036 | 20 | | PA | | 2-1 | 23-51-14 | TB0139T | C172 | 2 | | GDX0011 | S.. | 2 | | 278-299 |
| 037 | 24 | | PK | | 3-0 | 23-51-14 | TB0139T | A173 | 2 | | TB0139H | 73 | 2 | | ALL |
| 038 | 20 | | PA | | 3-0 | 23-51-14 | TB0139T | C173 | 2 | | GDX0011 | S.. | 2 | | 050-099, 150-199, 275-277 |
| 038 | 20 | | PA | | 2-1 | 23-51-14 | TB0139T | C173 | 2 | | GDX0011 | S.. | 2 | | 278-299 |
| 039 | 24 | | PK | | 4-0 | 23-51-14 | TB0139T | A174 | 2 | | TB0139H | 87 | 2 | | 050-099, 150-199, 275-277 |
| 039 | 24 | | PK | | 3-0 | 23-51-14 | TB0139T | A174 | 2 | | TB0139H | 87 | 2 | | 278-299 |
| 040 | 20 | | PA | | 3-0 | 23-51-14 | TB0139T | C174 | 2 | | GDX0011 | S.. | 2 | | 050-099, 150-199, 275-277 |
| 040 | 20 | | PA | | 2-1 | 23-51-14 | TB0139T | C174 | 2 | | GDX0011 | S.. | 2 | | 278-299 |
| 041 | 24 | | PK | | 4-0 | 23-51-14 | TB0139T | A175 | 2 | | TB0139H | 64 | 2 | | 050-099, 150-199, 275-277 |
| 041 | 24 | | PK | | 3-0 | 23-51-14 | TB0139T | A175 | 2 | | TB0139H | 64 | 2 | | 278-299 |
| 042 | 20 | | PA | | 3-0 | 23-51-14 | TB0139T | C175 | 2 | | GDX0011 | S.. | 2 | | 050-099, 150-199, 275-277 |
| 042 | 20 | | PA | | 2-1 | 23-51-14 | TB0139T | C175 | 2 | | GDX0011 | S.. | 2 | | 278-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 79

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 043 | 24 | | PK | 4-0 | 23-51-14 | TB0139T | A176 | 2 | | TB0139H | 57 | 2 | | 050-099, 150-199, 275-277 | | |
| 043 | 24 | | PK | 2-10 | 23-51-14 | TB0139T | A176 | 2 | | TB0139H | 57 | 2 | | 278-299 | | |
| 044 | 20 | | PA | 3-0 | 23-51-14 | TB0139T | C176 | 2 | | GDX0011 | S.. | 2 | | 050-099, 150-199, 275-277 | | |
| 044 | 20 | | PA | 2-1 | 23-51-14 | TB0139T | C176 | 2 | | GDX0011 | S.. | 2 | | 278-299 | | |
| 051 | 24 | | PK | 4-0 | 23-12-11 | D00439B | D01 | | | TB0139G | 178 | 2 | | 050-099, 150-156, 162-166, 275-276 | | |
| 051 | 24 | | PK | 4-0 | 23-12-11 | D00439B | D01 | | | TB0139Y | A177 | BJ | | 157, 167-199, 277 | | |
| 051 | 24 | | PK | 2-11 | 23-12-11 | D00439B | D01 | | | TB0139Y | A177 | BJ | | 278-299 | | |
| 052 | 24 | | PK | 4-0 | 23-12-21 | D00443B | D01 | | | TB0139G | 179 | 2 | | 050-099, 150-156, 162-166, 275-276 | | |
| 052 | 24 | | PK | 4-0 | 23-12-21 | D00443B | D01 | | | TB0139Y | C177 | BJ | | 157, 167-199, 277 | | |
| 052 | 24 | | PK | 2-8 | 23-12-21 | D00443B | D01 | | | TB0139Y | C177 | BJ | | 278-299 | | |
| 053 | 24 | | PK | 4-0 | 23-12-31 | D00445B | D01 | | | TB0139G | 180 | 2 | | 050-099, 150-156, 162-166, 275-276 | | |
| 053 | 24 | | PK | 4-0 | 23-12-31 | D00445B | D01 | | | TB0139Y | A178 | BJ | | 157, 167-199, 277 | | |
| 053 | 24 | | PK | 2-8 | 23-12-31 | D00445B | D01 | | | TB0139Y | A178 | BJ | | 278-299 | | |
| 054 | 24 | | PK | 4-0 | 23-21-11 | D05001P | | 23 | | TB0139G | 180 | 2 | | 050-099, 150-156, 162-166, 275-276 | | |
| 054 | 24 | | PK | 4-0 | 23-21-11 | D05001P | | 23 | | TB0139Y | A178 | BJ | | 157, 167-199, 277 | | |
| 054 | 24 | | PK | 2-11 | 23-21-11 | D05001P | | 23 | | TB0139Y | A178 | BJ | | 278-299 | | |
| 056 | 20 | | PA | 3-0 | 23-22-11 | D00447C | | 11 | | GDX0009 | D.. | 2 | | 050-099, 150-199, 275-277 | | |
| 056 | 20 | | PA | 2-2 | 23-22-11 | D00447C | | 11 | | GDX0009 | D.. | 2 | | 278-299 | | |
| 057 | 20 | | PA | 3-0 | 23-22-11 | D00447C | | 8 | | GDX0009 | S.. | 2 | | 050-099, 150-199, 275-277 | | |
| 057 | 20 | | PA | 2-2 | 23-22-11 | D00447C | | 8 | | GDX0009 | S.. | 2 | | 278-299 | | |
| 058 | 20 | | PQ CH | 5-0 | 23-22-11 | D00447C | | 10 | | D05109P | | 1 | | 050-099, 151, 275-276 | | |
| 058 | 20 | | PQ CH | 5-0 | 23-22-11 | TB0139G | | 163 | 2 | D05109P | | 1 | | 150, 152-199 | | |
| 058 | 20 | | PQ CH | 5-0 | 23-22-11 | TB0139G | | 162 | 2 | D05109P | | 1 | | 277 | | |
| 058 | 20 | | PQ CH | 4-6 | 23-22-11 | TB0139G | | 162 | 2 | D05109P | | 1 | | 278 | | |
| 058 | 20 | | PQ CH | 4-5 | 23-22-11 | TB0139G | | 162 | 2 | D05109P | | 1 | | 280-299 | | |
| 058Z | | | CH | 0-0 | 23-22-11 | D00447C | | DED | | D05109P | | DED | | 050-099, 151, 275-276 | | |
| 058Z | | | CH | 0-0 | 23-22-11 | TB0139G | | DED | | D05109P | | DED | | 150, 152-199, 277-299 | | |
| 069 | 24 | | PK | 4-0 | 23-51-21 | D04603P | | 23 | | TB0139H | 89 | 2 | | 050-099, 150-199, 275-277 | | |
| 069 | 24 | | PK | 3-5 | 23-51-21 | D04603P | | 23 | | TB0139H | 89 | 2 | | 278-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 80

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 079 | 24 | | PK | | 4-0 | 23-51-41 | D04607P | | 23 | | TB0139H | 89 | 2 | | 050-099, 150-199, 275-277 |
| 079 | 24 | | PK | | 3-4 | 23-51-41 | D04607P | | 23 | | TB0139H | 89 | 2 | | 278-299 |
| 082 | 24 | | PK | | 4-0 | 31-31-17 | D04813P | | 3 | | TB0139G | 180 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 082 | 24 | | PK | | 4-0 | 31-31-17 | D04813P | | 3 | | TB0139Y | A178 | BJ | | 157, 167-199, 277 |
| 082 | 24 | | PK | | 2-4 | 31-31-17 | D04813P | | 3 | | TB0139Y | A178 | BJ | | 278-299 |
| 088 | 24 | | PK | | 4-0 | 23-22-12 | D00447A | F07 | | | TB0139G | 170 | 2 | | 050-099, 150-199, 275-277 |
| 088 | 24 | | PK | | 2-9 | 23-22-12 | D00447A | F07 | | | TB0139G | 170 | 2 | | 278-299 |
| 091 | 24 | | PK | | 4-0 | 23-22-12 | D00447A | C07 | | | D00445B | D11 | | | 050-099 |
| 091 | 24 | | PK | | 4-0 | 23-22-12 | D00445B | D11 | | | D00447A | C07 | | | 150-166, 275-277 |
| 091 | 24 | | PK | | 4-0 | 23-22-12 | D00445B | D11 | | | TB0139D | A166 | 2 | | 167-199 |
| 091 | 24 | | PK | | 3-2 | 23-22-12 | D00445B | D11 | | | D00447A | C07 | | | 278-299 |
| 092 | 24 | | PK | | 4-0 | 23-22-12 | D00447A | H05 | | | D00445B | D07 | | | 050-099 |
| 092 | 24 | | PK | | 4-0 | 23-22-12 | D00445B | D07 | | | D00447A | H05 | | | 150-199, 275-277 |
| 092 | 24 | | PK | | 3-2 | 23-22-12 | D00445B | D07 | | | D00447A | H05 | | | 278-299 |
| 093 | 24 | | PK | | 4-0 | 23-22-12 | D00447A | K07 | | | D00445B | D08 | | | 050-099 |
| 093 | 24 | | PK | | 4-0 | 23-22-12 | D00445B | D08 | | | D00447A | K07 | | | 150-199, 275-277 |
| 093 | 24 | | PK | | 3-2 | 23-22-12 | D00445B | D08 | | | D00447A | K07 | | | 278-299 |
| 094 | 24 | | PK | | 4-0 | 23-31-13 | D05029P | | 3 | | TB0139F | A103 | 2 | | 050-099 |
| 094 | 24 | | PK | | 6-0 | 23-31-13 | D05029P | | 3 | | TB0139F | A103 | 2 | | 150-199, 275-277 |
| 094 | 24 | | PK | | 3-0 | 23-31-13 | D05029P | | 3 | | TB0139F | A103 | 2 | | 278-299 |
| 095 | 24 | | PK | | 4-0 | 23-31-13 | D05029P | | 2 | | TB0139G | 106 | 2 | | 050-099, 150-199 |
| 095 | 24 | | PK | | 6-0 | 23-31-13 | D05029P | | 2 | | TB0139F | C103 | 2 | | 275-277 |
| 095 | 24 | | PK | | 3-0 | 23-31-13 | D05029P | | 2 | | TB0139F | C103 | 2 | | 278-299 |
| 096 | 24 | | PK | | 4-0 | 23-31-13 | D05029P | | 1 | | TB0139G | 104 | 2 | | 050-099 |
| 096 | 24 | | PK | | 6-0 | 23-31-13 | D05029P | | 1 | | TB0139G | 104 | 2 | | 150-199, 275-277 |
| 096 | 24 | | PK | | 3-0 | 23-31-13 | D05029P | | 1 | | TB0139G | 104 | 2 | | 278-299 |
| 097 | 22 | | PQ | DV | 4-0 | 23-34-11 | D04213P | | 5 | | TB0139G | 107 | 2 | | 050-099, 150-199, 275-277 |
| 097 | 22 | | PQ | DV | 3-3 | 23-34-11 | D04213P | | 5 | | TB0139G | 107 | 2 | | 278-299 |
| 097Z | | | | DV | 0-0 | 23-34-11 | D04213P | DED | | | TB0139G | DED | | | ALL |
| 098 | 22 | | PA | | 6-0 | 23-42-11 | D05001P | | 1 | | TB0139F | A135 | 2 | | 050-099 |
| 098 | 22 | | PA | | 5-0 | 23-42-11 | D05001P | | 1 | | TB0139F | A135 | 2 | | 150-199, 275-277 |
| 098 | 22 | | PA | | 4-3 | 23-42-11 | D05001P | | 1 | | TB0139F | A135 | 2 | | 278-299 |
| 099 | 22 | | PA | | 6-0 | 23-42-11 | D05001P | | 2 | | TB0139F | C135 | 2 | | 050-099 |
| 099 | 22 | | PA | | 5-0 | 23-42-11 | D05001P | | 2 | | TB0139F | C135 | 2 | | 150-199, 275-277 |
| 099 | 22 | | PA | | 4-3 | 23-42-11 | D05001P | | 2 | | TB0139F | C135 | 2 | | 278-299 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 81
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 100 | 22 | | PA | | 6-0 | 23-42-11 | D05001P | | | | TB0139F | A136 | 2 | | 050-099 |
| 100 | 22 | | PA | | 5-0 | 23-42-11 | D05001P | | | | TB0139F | A136 | 2 | | 150-199, 275-277 |
| 100 | 22 | | PA | | 4-3 | 23-42-11 | D05001P | | | | TB0139F | A136 | 2 | | 278-299 |
| 101 | 22 | | PA | | 6-0 | 23-42-11 | D05001P | | | | TB0139F | C136 | 2 | | 050-099 |
| 101 | 22 | | PA | | 5-0 | 23-42-11 | D05001P | | | | TB0139F | C136 | 2 | | 150-199, 275-277 |
| 101 | 22 | | PA | | 4-3 | 23-42-11 | D05001P | | | | TB0139F | C136 | 2 | | 278-299 |
| 102 | 22 | | PQ | EB | 6-0 | 23-42-11 | D05001P | | | | TB0139F | A137 | 2 | | 050-099 |
| 102 | 22 | | PQ | EB | 5-0 | 23-42-11 | D05001P | | | | TB0139F | A137 | 2 | | 150-199, 275-277 |
| 102 | 22 | | PQ | EB | 4-3 | 23-42-11 | D05001P | | | | TB0139F | A137 | 2 | | 278-299 |
| 102Z | | | | EB | 0-0 | 23-42-11 | D05001P | | | | TB0139F | C137 | 2 | | ALL |
| 103 | 16 | | PA | | 5-0 | 23-12-31 | D04213P | | | | TB0139G | 146 | 2 | | 050-099, 150-199, 275-277 |
| 103 | 16 | | PA | | 4-0 | 23-12-31 | D04213P | | | | TB0139G | 146 | 2 | | 278-299 |
| 104 | 16 | | PA | | 6-0 | 23-12-31 | D00445C | | | | TB0139G | 146 | 2 | | 050-099 |
| 104 | 16 | | PA | | 5-0 | 23-12-31 | D00445C | | | | TB0139G | 146 | 2 | | 150-199, 275-277 |
| 104 | 16 | | PA | | 3-6 | 23-12-31 | D00445C | | | | TB0139G | 146 | 2 | | 278-299 |
| 105 | 18 | | PA | | 4-0 | 23-12-31 | D04931P | | | | TB0139G | 146 | 2 | | 050-099, 150-199, 275-277 |
| 105 | 18 | | PA | | 2-11 | 23-12-31 | D04931P | | | | TB0139G | 146 | 2 | | 278-299 |
| 106 | 16 | | PA | | 3-0 | 23-12-31 | D00445C | | | | GDX0011 | D.. | 2 | | 050-099, 150-199, 275-277 |
| 106 | 16 | | PA | | 2-1 | 23-12-31 | D00445C | | | | GDX0011 | D.. | 2 | | 278-299 |
| 107 | 22 | | PA | | 3-0 | 23-12-31 | D00445B | | D03 | | GDX0011 | D.. | 2 | | 050-099, 150-199, 275-277 |
| 107 | 22 | | PA | | 2-1 | 23-12-31 | D00445B | | D03 | | GDX0011 | D.. | 2 | | 278-299 |
| 108 | 24 | | PK | | 4-0 | 23-51-14 | D04601P | | | | TB0139H | 89 | 2 | | 050-099, 150-199, 275-277 |
| 108 | 24 | | PK | | 3-2 | 23-51-14 | D04601P | | | | TB0139H | 89 | 2 | | 278-299 |
| 109 | 22 | | PA | | 4-1 | 23-42-11 | D05001P | | | | TB0139F | C140 | 2 | | 280-299 |
| 110 | 22 | | PA | | 6-0 | 23-43-11 | D05001P | | | | TB0139F | A119 | 2 | | 050-099, 150-199, 275-277 |
| 110 | 22 | | PA | | 5-0 | 23-43-11 | D05001P | | | | TB0139F | A119 | 2 | | 278-299 |
| 111 | 22 | | PA | | 6-0 | 23-43-11 | D05001P | | | | TB0139F | C119 | 2 | | 050-099, 150-199, 275-277 |
| 111 | 22 | | PA | | 5-0 | 23-43-11 | D05001P | | | | TB0139F | C119 | 2 | | 278-299 |
| 112 | 22 | | PA | | 6-0 | 23-43-11 | D05001P | | | | TB0139D | C124 | 2 | | 050-099, 150-199, 275-277 |
| 112 | 22 | | PA | | 5-0 | 23-43-11 | D05001P | | | | TB0139D | C124 | 2 | | 278-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 82

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 113 | 20 | | PA | 5-0 | 23-51-11 | D04601P | | 1 | | | GDX0003 | S.. | 2 | | 050-099, 150-199, 275-277 | |
| 113 | 20 | | PA | 4-5 | 23-51-11 | D04601P | | 1 | | | GDX0003 | S.. | 2 | | 278-299 | |
| 114 | 20 | | PA | 5-0 | 23-51-11 | D04601P | | 4 | | | GDX0003 | S.. | 2 | | 050-099, 150-199, 275-277 | |
| 114 | 20 | | PA | 4-5 | 23-51-11 | D04601P | | 4 | | | GDX0003 | S.. | 2 | | 278-299 | |
| 116 | 24 | | PK | 6-0 | 23-51-11 | D04601P | | 26 | | | TB0139Z | 11 | BJ | | 050-099, 150-199 | |
| 116 | 24 | | PK | 6-0 | 23-51-11 | D04601P | | 26 | | | TB0139H | 11 | 2 | | 275-277 | |
| 116 | 24 | | PK | 6-1 | 23-51-11 | D04601P | | 26 | | | TB0139H | 11 | 2 | | 278-299 | |
| 117 | 24 | | PK | 4-0 | 23-51-14 | D04601P | | 25 | | | TB0139H | 75 | 2 | | 050-099 | |
| 117 | 24 | | PK | 6-0 | 23-51-14 | D04601P | | 25 | | | TB0139H | 75 | 2 | | 150-199, 275-277 | |
| 117 | 24 | | PK | 3-8 | 23-51-14 | D04601P | | 25 | | | TB0139H | 75 | 2 | | 278-299 | |
| 119 | 24 | | PK | 4-0 | 23-51-14 | D04601P | | 21 | | | TB0139H | 83 | 2 | | 050-099 | |
| 119 | 24 | | PK | 6-0 | 23-51-14 | D04601P | | 21 | | | TB0139H | 83 | 2 | | 150-199, 275-277 | |
| 119 | 24 | | PK | 3-2 | 23-51-14 | D04601P | | 21 | | | TB0139H | 83 | 2 | | 278-299 | |
| 120 | 20 | | PA | 5-0 | 23-51-11 | D04601P | | 20 | | | GDX0003 | S.. | 2 | | 050-099, 150-199, 275-277 | |
| 120 | 20 | | PA | 4-5 | 23-51-11 | D04601P | | 20 | | | GDX0003 | S.. | 2 | | 278-299 | |
| 121 | 24 | | PK | 6-0 | 23-51-12 | D04601P | | 35 | | | TB0139Z | 27 | BJ | | 050-099, 150-199 | |
| 121 | 24 | | PK | 6-0 | 23-51-12 | D04601P | | 35 | | | TB0139H | 29 | 2 | | 275-277 | |
| 121 | 24 | | PK | 4-7 | 23-51-12 | D04601P | | 35 | | | TB0139H | 29 | 2 | | 278-299 | |
| 122 | 24 | | PK | 6-0 | 23-51-12 | D04601P | | 36 | | | TB0139G | 28 | 2 | | 050-099, 150-199 | |
| 122 | 24 | | PK | 6-0 | 23-51-12 | D04601P | | 36 | | | TB0139H | 31 | 2 | | 275-277 | |
| 122 | 24 | | PK | 4-7 | 23-51-12 | D04601P | | 36 | | | TB0139H | 31 | 2 | | 278-299 | |
| 124 | 24 | | PK | 6-0 | 23-51-12 | D04601P | | 37 | | | TB0139G | 29 | 2 | | 050-099, 150-199 | |
| 124 | 24 | | PK | 6-0 | 23-51-12 | D04601P | | 37 | | | TB0139H | 34 | 2 | | 275-277 | |
| 124 | 24 | | PK | 4-7 | 23-51-12 | D04601P | | 37 | | | TB0139H | 34 | 2 | | 278-299 | |
| 125 | 24 | | PK | 5-0 | 23-51-12 | D04601P | | 31 | | | TB0139H | 36 | 2 | | 050-099 | |
| 125 | 24 | | PK | 6-0 | 23-51-12 | D04601P | | 31 | | | TB0139H | 36 | 2 | | 150-199, 275-277 | |
| 125 | 24 | | PK | 4-7 | 23-51-12 | D04601P | | 31 | | | TB0139H | 36 | 2 | | 278-299 | |
| 126 | 24 | | PK | 5-0 | 23-51-12 | D04601P | | 30 | | | TB0139H | 38 | 2 | | 050-099 | |
| 126 | 24 | | PK | 6-0 | 23-51-12 | D04601P | | 30 | | | TB0139H | 38 | 2 | | 150-199, 275-277 | |
| 126 | 24 | | PK | 4-7 | 23-51-12 | D04601P | | 30 | | | TB0139H | 38 | 2 | | 278-299 | |
| 128 | 24 | | PK | 5-0 | 23-51-12 | D04601P | | 27 | | | TB0139H | 41 | 2 | | 050-099 | |
| 128 | 24 | | PK | 6-0 | 23-51-12 | D04601P | | 27 | | | TB0139H | 41 | 2 | | 150-199, 275-277 | |
| 128 | 24 | | PK | 4-4 | 23-51-12 | D04601P | | 27 | | | TB0139H | 41 | 2 | | 278-299 | |
| 129 | 24 | | PK | 5-0 | 23-51-12 | D04601P | | 29 | | | TB0139H | 43 | 2 | | 050-099 | |
| 129 | 24 | | PK | 6-0 | 23-51-12 | D04601P | | 29 | | | TB0139H | 43 | 2 | | 150-199, 275-277 | |
| 129 | 24 | | PK | 4-4 | 23-51-12 | D04601P | | 29 | | | TB0139H | 43 | 2 | | 278-299 | |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 83
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 130 | 24 | | PK | 5-0 | 23-51-13 | D04601P | | 34 | | | TB0139H | 45 | 2 | | 050-099 | |
| 130 | 24 | | PK | 6-0 | 23-51-13 | D04601P | | 34 | | | TB0139H | 45 | 2 | | 150-199, 275-277 | |
| 130 | 24 | | PK | 4-4 | 23-51-13 | D04601P | | 34 | | | TB0139H | 45 | 2 | | 278-299 | |
| 131 | 24 | | PK | 5-0 | 23-51-13 | D04601P | | 33 | | | TB0139H | 48 | 2 | | 050-099 | |
| 131 | 24 | | PK | 6-0 | 23-51-13 | D04601P | | 33 | | | TB0139H | 48 | 2 | | 150-199, 275-277 | |
| 131 | 24 | | PK | 4-4 | 23-51-13 | D04601P | | 33 | | | TB0139H | 48 | 2 | | 278-299 | |
| 132 | 24 | | PK | 5-0 | 23-51-13 | D04601P | | 32 | | | TB0139H | 51 | 2 | | 050-099 | |
| 132 | 24 | | PK | 6-0 | 23-51-13 | D04601P | | 32 | | | TB0139H | 51 | 2 | | 150-199, 275-277 | |
| 132 | 24 | | PK | 4-0 | 23-51-13 | D04601P | | 32 | | | TB0139H | 51 | 2 | | 278-299 | |
| 133 | 24 | | PK | 5-0 | 23-51-13 | D04601P | | 28 | | | TB0139H | 53 | 2 | | 050-099 | |
| 133 | 24 | | PK | 6-0 | 23-51-13 | D04601P | | 28 | | | TB0139H | 53 | 2 | | 150-199, 275-277 | |
| 133 | 24 | | PK | 4-0 | 23-51-13 | D04601P | | 28 | | | TB0139H | 53 | 2 | | 278-299 | |
| 135 | 24 | | PK | 5-0 | 23-51-14 | D04601P | | 14 | | | TB0139H | 55 | 2 | | 050-099 | |
| 135 | 24 | | PK | 6-0 | 23-51-14 | D04601P | | 14 | | | TB0139H | 55 | 2 | | 150-199, 275-277 | |
| 135 | 24 | | PK | 4-0 | 23-51-14 | D04601P | | 14 | | | TB0139H | 55 | 2 | | 278-299 | |
| 136 | 24 | | PK | 6-0 | 23-51-14 | D04601P | | 15 | | | TB0139H | 57 | 2 | | 050-099, 150-199, 275-277 | |
| 136 | 24 | | PK | 4-0 | 23-51-14 | D04601P | | 15 | | | TB0139H | 57 | 2 | | 278-299 | |
| 137 | 24 | | PK | 6-0 | 23-51-14 | D04601P | | 24 | | | TB0139H | 59 | 2 | | 050-099, 150-199, 275-277 | |
| 137 | 24 | | PK | 4-0 | 23-51-14 | D04601P | | 24 | | | TB0139H | 59 | 2 | | 278-299 | |
| 138 | 24 | | PK | 6-0 | 23-51-14 | D04601P | | 10 | | | TB0139H | 62 | 2 | | 050-099, 150-199, 275-277 | |
| 138 | 24 | | PK | 3-8 | 23-51-14 | D04601P | | 10 | | | TB0139H | 62 | 2 | | 278-299 | |
| 139 | 24 | | PK | 6-0 | 23-51-14 | D04601P | | 11 | | | TB0139H | 64 | 2 | | 050-099, 150-199, 275-277 | |
| 139 | 24 | | PK | 3-8 | 23-51-14 | D04601P | | 11 | | | TB0139H | 64 | 2 | | 278-299 | |
| 140 | 24 | | PK | 6-0 | 23-51-14 | D04601P | | 22 | | | TB0139H | 66 | 2 | | 050-099, 150-199, 275-277 | |
| 140 | 24 | | PK | 3-8 | 23-51-14 | D04601P | | 22 | | | TB0139H | 66 | 2 | | 278-299 | |
| 142 | 20 | | PA | 5-0 | 23-51-21 | GDX0003 | | S.. | 2 | | D04603P | 20 | | | 050-099, 150-199, 275-277 | |
| 142 | 20 | | PA | 4-8 | 23-51-21 | GDX0003 | | S.. | 2 | | D04603P | 20 | | | 278-299 | |
| 143 | 24 | | PK | 7-0 | 23-51-21 | TB0139Z | | 11 | BJ | | D04603P | 26 | | | 050-099 | |
| 143 | 24 | | PK | 6-0 | 23-51-21 | TB0139Z | | 11 | BJ | | D04603P | 26 | | | 150-199 | |
| 143 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | | 11 | 2 | | D04603P | 26 | | | 275-277 | |
| 143 | 24 | | PK | 6-4 | 23-51-21 | TB0139H | | 11 | 2 | | D04603P | 26 | | | 278-299 | |
| 144 | 24 | | PK | 5-0 | 23-51-21 | TB0139H | | 75 | 2 | | D04603P | 25 | | | 050-099 | |
| 144 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | | 75 | 2 | | D04603P | 25 | | | 150-199, 275-277 | |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 144 | 24 | | PK | 3-10 | 23-51-21 | TB0139H | 75 | 2 | | D04603P | 25 | | | 278-299 | | |
| 145 | 24 | | PK | 4-0 | 23-51-21 | TB0139H | 83 | 2 | | D04603P | 21 | | | 050-099 | | |
| 145 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 83 | 2 | | D04603P | 21 | | | 150-199, 275-277 | | |
| 145 | 24 | | PK | 3-5 | 23-51-21 | TB0139H | 83 | 2 | | D04603P | 21 | | | 278-299 | | |
| 146 | 24 | | PK | 5-0 | 23-51-21 | TB0139H | 53 | 2 | | D04603P | 28 | | | 050-099 | | |
| 146 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 53 | 2 | | D04603P | 28 | | | 150-199, 275-277 | | |
| 146 | 24 | | PK | 4-2 | 23-51-21 | TB0139H | 53 | 2 | | D04603P | 28 | | | 278-299 | | |
| 147 | 24 | | PK | 5-0 | 23-51-21 | TB0139H | 45 | 2 | | D04603P | 34 | | | 050-099 | | |
| 147 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 45 | 2 | | D04603P | 34 | | | 150-199, 275-277 | | |
| 147 | 24 | | PK | 4-6 | 23-51-21 | TB0139H | 45 | 2 | | D04603P | 34 | | | 278-299 | | |
| 148 | 24 | | PK | 5-0 | 23-51-21 | TB0139H | 48 | 2 | | D04603P | 33 | | | 050-099 | | |
| 148 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 48 | 2 | | D04603P | 33 | | | 150-199, 275-277 | | |
| 148 | 24 | | PK | 4-6 | 23-51-21 | TB0139H | 48 | 2 | | D04603P | 33 | | | 278-299 | | |
| 149 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 51 | 2 | | D04603P | 32 | | | 050-099, 150-199, 275-277 | | |
| 149 | 24 | | PK | 4-2 | 23-51-21 | TB0139H | 51 | 2 | | D04603P | 32 | | | 278-299 | | |
| 150 | 24 | | PK | 6-0 | 23-51-21 | TB0139G | 28 | 2 | | D04603P | 36 | | | 050-099, 150-199 | | |
| 150 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 31 | 2 | | D04603P | 36 | | | 275-277 | | |
| 150 | 24 | | PK | 4-9 | 23-51-21 | TB0139H | 31 | 2 | | D04603P | 36 | | | 278-299 | | |
| 151 | 24 | | PK | 5-0 | 23-51-21 | TB0139H | 38 | 2 | | D04603P | 30 | | | 050-099 | | |
| 151 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 38 | 2 | | D04603P | 30 | | | 150-199, 275-277 | | |
| 151 | 24 | | PK | 4-9 | 23-51-21 | TB0139H | 38 | 2 | | D04603P | 30 | | | 278-299 | | |
| 152 | 24 | | PK | 6-0 | 23-51-21 | TB0139G | 29 | 2 | | D04603P | 37 | | | 050-099, 150-199 | | |
| 152 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 34 | 2 | | D04603P | 37 | | | 275-277 | | |
| 152 | 24 | | PK | 4-9 | 23-51-21 | TB0139H | 34 | 2 | | D04603P | 37 | | | 278-299 | | |
| 153 | 24 | | PK | 5-0 | 23-51-21 | TB0139H | 43 | 2 | | D04603P | 29 | | | 050-099 | | |
| 153 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 43 | 2 | | D04603P | 29 | | | 150-199, 275-277 | | |
| 153 | 24 | | PK | 4-6 | 23-51-21 | TB0139H | 43 | 2 | | D04603P | 29 | | | 278-299 | | |
| 154 | 24 | | PK | 6-0 | 23-51-21 | TB0139Z | 27 | BJ | | D04603P | 35 | | | 050-099, 150-199 | | |
| 154 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 29 | 2 | | D04603P | 35 | | | 275-277 | | |
| 154 | 24 | | PK | 4-9 | 23-51-21 | TB0139H | 29 | 2 | | D04603P | 35 | | | 278-299 | | |
| 155 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 36 | 2 | | D04603P | 31 | | | 050-099, 150-199, 275-277 | | |
| 155 | 24 | | PK | 4-9 | 23-51-21 | TB0139H | 36 | 2 | | D04603P | 31 | | | 278-299 | | |
| 156 | 24 | | PK | 5-0 | 23-51-21 | TB0139H | 41 | 2 | | D04603P | 27 | | | 050-099 | | |
| 156 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 41 | 2 | | D04603P | 27 | | | 150-199, 275-277 | | |
| 156 | 24 | | PK | 4-6 | 23-51-21 | TB0139H | 41 | 2 | | D04603P | 27 | | | 278-299 | | |
| 157 | 20 | | PA | 5-0 | 23-51-21 | GDX0003 | S.. | 2 | | D04603P | 1 | | | 050-099, 150-199, 275-277 | | |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 85
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 157 | 20 | | PA | 4-8 | 23-51-21 | GDX0003 | S.. | 2 | | D04603P | | | 1 | | 278-299 | |
| 158 | 20 | | PA | 5-0 | 23-51-21 | GDX0003 | S.. | 2 | | D04603P | | | 4 | | 050-099, 150-199, 275-277 | |
| 158 | 20 | | PA | 4-8 | 23-51-21 | GDX0003 | S.. | 2 | | D04603P | | | 4 | | 278-299 | |
| 159 | 24 | | PK | 3-0 | 23-21-11 | TB0139G | 169 | 2 | | TB0139D | A168 | 2 | | | 150, 152-199, 277-299 | |
| 160 | 24 | | PK | 5-0 | 23-51-21 | TB0139H | 55 | 2 | | D04603P | | | 14 | | 050-099 | |
| 160 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 55 | 2 | | D04603P | | | 14 | | 150-199, 275-277 | |
| 160 | 24 | | PK | 4-2 | 23-51-21 | TB0139H | 55 | 2 | | D04603P | | | 14 | | 278-299 | |
| 161 | 24 | | PK | 5-0 | 23-51-21 | TB0139H | 57 | 2 | | D04603P | | | 15 | | 050-099 | |
| 161 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 57 | 2 | | D04603P | | | 15 | | 150-199, 275-277 | |
| 161 | 24 | | PK | 4-2 | 23-51-21 | TB0139H | 57 | 2 | | D04603P | | | 15 | | 278-299 | |
| 162 | 24 | | PK | 5-0 | 23-51-21 | TB0139H | 59 | 2 | | D04603P | | | 24 | | 050-099 | |
| 162 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 59 | 2 | | D04603P | | | 24 | | 150-199, 275-277 | |
| 162 | 24 | | PK | 4-2 | 23-51-21 | TB0139H | 59 | 2 | | D04603P | | | 24 | | 278-299 | |
| 163 | 24 | | PK | 5-0 | 23-51-21 | D04603P | 10 | | | TB0139H | | 2 | 62 | | 050-099 | |
| 163 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 62 | 2 | | D04603P | | | 10 | | 150-199, 275-277 | |
| 163 | 24 | | PK | 3-10 | 23-51-21 | TB0139H | 62 | 2 | | D04603P | | | 10 | | 278-299 | |
| 164 | 24 | | PK | 5-0 | 23-51-21 | D04603P | 11 | | | TB0139H | | 2 | 64 | | 050-099 | |
| 164 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 64 | 2 | | D04603P | | | 11 | | 150-199, 275-277 | |
| 164 | 24 | | PK | 3-10 | 23-51-21 | TB0139H | 64 | 2 | | D04603P | | | 11 | | 278-299 | |
| 165 | 24 | | PK | 5-0 | 23-51-21 | D04603P | 22 | | | TB0139H | | 2 | 66 | | 050-099 | |
| 165 | 24 | | PK | 6-0 | 23-51-21 | TB0139H | 66 | 2 | | D04603P | | | 22 | | 150-199, 275-277 | |
| 165 | 24 | | PK | 3-10 | 23-51-21 | TB0139H | 66 | 2 | | D04603P | | | 22 | | 278-299 | |
| 166 | 20 | | PA | 5-0 | 23-51-41 | D04607P | 20 | | | GDX0003 | | 2 | S.. | | 050-099, 150-199, 275-277 | |
| 166 | 20 | | PA | 4-7 | 23-51-41 | D04607P | 20 | | | GDX0003 | | 2 | S.. | | 278-299 | |
| 167 | 24 | | PK | 7-0 | 23-51-41 | D04607P | 26 | | | TB0139Z | | BJ | 11 | | 050-099 | |
| 167 | 24 | | PK | 6-0 | 23-51-41 | D04607P | 26 | | | TB0139Z | | BJ | 11 | | 150-199 | |
| 167 | 24 | | PK | 6-0 | 23-51-41 | D04607P | 26 | | | TB0139H | | 2 | 11 | | 275-277 | |
| 167 | 24 | | PK | 6-3 | 23-51-41 | D04607P | 26 | | | TB0139H | | 2 | 11 | | 278-299 | |
| 168 | 24 | | PK | 5-0 | 23-51-41 | D04607P | 25 | | | TB0139H | | 2 | 75 | | 050-099 | |
| 168 | 24 | | PK | 4-0 | 23-51-41 | D04607P | 25 | | | TB0139H | | 2 | 75 | | 150-199, 275-277 | |
| 168 | 24 | | PK | 3-10 | 23-51-41 | D04607P | 25 | | | TB0139H | | 2 | 75 | | 278-299 | |
| 169 | 24 | | PK | 4-0 | 23-51-41 | D04607P | 21 | | | TB0139H | | 2 | 83 | | 050-099, 150-199, 275-277 | |
| 169 | 24 | | PK | 3-4 | 23-51-41 | D04607P | 21 | | | TB0139H | | 2 | 83 | | 278-299 | |
| 170 | 24 | | PK | 5-0 | 23-51-41 | D04607P | 28 | | | TB0139H | | 2 | 53 | | 050-099, 150-199, 275-277 | |
| 170 | 24 | | PK | 4-2 | 23-51-41 | D04607P | 28 | | | TB0139H | | 2 | 53 | | 278-299 | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 86

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 171 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 34 | | | TB0139H | 45 | 2 | | 050-099, 150-199, 275-277 | |
| 171 | 24 | | PK | 4-6 | 23-51-41 | D04607P | | 34 | | | TB0139H | 45 | 2 | | 278-299 | |
| 172 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 33 | | | TB0139H | 48 | 2 | | 050-099, 150-199, 275-277 | |
| 172 | 24 | | PK | 4-6 | 23-51-41 | D04607P | | 33 | | | TB0139H | 48 | 2 | | 278-299 | |
| 173 | 24 | | PK | 6-0 | 23-51-41 | D04607P | | 32 | | | TB0139H | 51 | 2 | | 050-099 | |
| 173 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 32 | | | TB0139H | 51 | 2 | | 150-199, 275-277 | |
| 173 | 24 | | PK | 4-2 | 23-51-41 | D04607P | | 32 | | | TB0139H | 51 | 2 | | 278-299 | |
| 174 | 24 | | PK | 6-0 | 23-51-41 | D04607P | | 36 | | | TB0139G | 28 | 2 | | 050-099, 150-199 | |
| 174 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 36 | | | TB0139H | 31 | 2 | | 275-277 | |
| 174 | 24 | | PK | 4-9 | 23-51-41 | D04607P | | 36 | | | TB0139H | 31 | 2 | | 278-299 | |
| 175 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 30 | | | TB0139H | 38 | 2 | | 050-099, 150-199, 275-277 | |
| 175 | 24 | | PK | 4-9 | 23-51-41 | D04607P | | 30 | | | TB0139H | 38 | 2 | | 278-299 | |
| 176 | 24 | | PK | 6-0 | 23-51-41 | D04607P | | 37 | | | TB0139G | 29 | 2 | | 050-099 | |
| 176 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 37 | | | TB0139G | 29 | 2 | | 150-199 | |
| 176 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 37 | | | TB0139H | 34 | 2 | | 275-277 | |
| 176 | 24 | | PK | 4-9 | 23-51-41 | D04607P | | 37 | | | TB0139H | 34 | 2 | | 278-299 | |
| 177 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 29 | | | TB0139H | 43 | 2 | | 050-099, 150-199, 275-277 | |
| 177 | 24 | | PK | 4-6 | 23-51-41 | D04607P | | 29 | | | TB0139H | 43 | 2 | | 278-299 | |
| 178 | 24 | | PK | 6-0 | 23-51-41 | D04607P | | 35 | | | TB0139Z | 27 | BJ | | 050-099, 150-199 | |
| 178 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 35 | | | TB0139H | 29 | 2 | | 275-277 | |
| 178 | 24 | | PK | 4-9 | 23-51-41 | D04607P | | 35 | | | TB0139H | 29 | 2 | | 278-299 | |
| 179 | 24 | | PK | 6-0 | 23-51-41 | D04607P | | 31 | | | TB0139H | 36 | 2 | | 050-099 | |
| 179 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 31 | | | TB0139H | 36 | 2 | | 150-199, 275-277 | |
| 179 | 24 | | PK | 4-9 | 23-51-41 | D04607P | | 31 | | | TB0139H | 36 | 2 | | 278-299 | |
| 180 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 27 | | | TB0139H | 41 | 2 | | 050-099, 150-199, 275-277 | |
| 180 | 24 | | PK | 4-6 | 23-51-41 | D04607P | | 27 | | | TB0139H | 41 | 2 | | 278-299 | |
| 181 | 20 | | PA | 5-0 | 23-51-41 | D04607P | | 4 | | | GDX0003 | S.. | 2 | | 050-099, 150-199, 275-277 | |
| 181 | 20 | | PA | 4-7 | 23-51-41 | D04607P | | 4 | | | GDX0003 | S.. | 2 | | 278-299 | |
| 182 | 20 | | PA | 5-0 | 23-51-41 | D04607P | | 1 | | | GDX0003 | S.. | 2 | | 050-099, 150-199, 275-277 | |
| 182 | 20 | | PA | 4-7 | 23-51-41 | D04607P | | 1 | | | GDX0003 | S.. | 2 | | 278-299 | |
| 183 | 24 | | PK | 4-0 | 23-22-12 | D00445B | | C07 | | | TB0139G | 170 | 2 | | 050-099, 150-199, 275-277 | |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 87
Mar 14/2007

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|-------------------|--------------------|-------|-------|---------------------------------|-------------|---------|-------|------|-----------|---------|-------|------|------|------------------------------|-------------|
| Wire No. | GA | CO TY | Fam | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 183 | 24 | | PK | 2-10 | 23-22-12 | D00445B | | C07 | | TB0139G | 170 | 2 | | 278-299 | |
| 184 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 14 | | TB0139H | 55 | 2 | | 050-099, 150-199, 275-277 | |
| 184 | 24 | | PK | 4-2 | 23-51-41 | D04607P | | 14 | | TB0139H | 55 | 2 | | 278-299 | |
| 185 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 15 | | TB0139H | 57 | 2 | | 050-099, 150-199, 275-277 | |
| 185 | 24 | | PK | 4-2 | 23-51-41 | D04607P | | 15 | | TB0139H | 57 | 2 | | 278-299 | |
| 186 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 24 | | TB0139H | 59 | 2 | | 050-099, 150-199, 275-277 | |
| 186 | 24 | | PK | 4-2 | 23-51-41 | D04607P | | 24 | | TB0139H | 59 | 2 | | 278-299 | |
| 187 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 10 | | TB0139H | 62 | 2 | | 050-099 | |
| 187 | 24 | | PK | 4-0 | 23-51-41 | D04607P | | 10 | | TB0139H | 62 | 2 | | 150-199, 275-277 | |
| 187 | 24 | | PK | 3-10 | 23-51-41 | D04607P | | 10 | | TB0139H | 62 | 2 | | 278-299 | |
| 188 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 11 | | TB0139H | 64 | 2 | | 050-099 | |
| 188 | 24 | | PK | 4-0 | 23-51-41 | D04607P | | 11 | | TB0139H | 64 | 2 | | 150-199, 275-277 | |
| 188 | 24 | | PK | 3-10 | 23-51-41 | D04607P | | 11 | | TB0139H | 64 | 2 | | 278-299 | |
| 189 | 24 | | PK | 5-0 | 23-51-41 | D04607P | | 22 | | TB0139H | 66 | 2 | | 050-099 | |
| 189 | 24 | | PK | 4-0 | 23-51-41 | D04607P | | 22 | | TB0139H | 66 | 2 | | 150-199, 275-277 | |
| 189 | 24 | | PK | 3-10 | 23-51-41 | D04607P | | 22 | | TB0139H | 66 | 2 | | 278-299 | |
| 201 | 20 | | UA | 1-6 | 23-12-11 | D00439B | | | FA | GDX0013 | S.. | 2 | | ALL | |
| 201B | 24 | | PW IA | 7-0 | 23-12-11 | D04927P | | 7 | | D00439B | B07 | | | 050-099, 150-199, 275-277 | |
| 201B | 24 | | PW IA | 6-8 | 23-12-11 | D04927P | | 7 | | D00439B | B07 | | | 278-299 | |
| 201R | 24 | | PW IA | 0-0 | 23-12-11 | D04927P | | 6 | | D00439B | A07 | | | ALL | |
| 201Z | 24 | | PW IA | 0-0 | 23-12-11 | D04927P | | 10 | | D00439B | | | FA | ALL | |
| 202 | 20 | | UA | 1-6 | 23-12-21 | D00443B | | | FB | GDX0013 | S.. | 2 | | ALL | |
| 202B | 24 | | PW IB | 4-0 | 23-12-21 | D04929P | | 2 | | D00443B | B07 | | | 050-099, 150-199, 275-277 | |
| 202B | 24 | | PW IB | 2-11 | 23-12-21 | D04929P | | 2 | | D00443B | B07 | | | 278-299 | |
| 202R | 24 | | PW IB | 0-0 | 23-12-21 | D04929P | | 1 | | D00443B | A07 | | | ALL | |
| 202Z | 24 | | PW IB | 0-0 | 23-12-21 | D04929P | | 3 | | D00443B | | | FB | ALL | |
| 203B | 24 | | PL IC | 4-0 | 23-21-11 | D00441B | | C02 | | D00439B | B13 | | | 050-099 | |
| 203B | 24 | | PL IC | 3-0 | 23-21-11 | D00441B | | C02 | | D00439B | B13 | | | 150-199, 275-277 | |
| 203B | 24 | | PL IC | 2-8 | 23-21-11 | D00441B | | C02 | | D00439B | B13 | | | 278-299 | |
| 203R | 24 | | PL IC | 0-0 | 23-21-11 | D00441B | | B02 | | D00439B | A13 | | | ALL | |
| 204B | 24 | | PL ID | 4-0 | 23-21-11 | D00441B | | B03 | | D00443B | B13 | | | 050-099 | |
| 204B | 24 | | PL ID | 3-0 | 23-21-11 | D00441B | | B03 | | D00443B | B13 | | | 150-199, 275-277 | |
| 204B | 24 | | PL ID | 2-9 | 23-21-11 | D00441B | | B03 | | D00443B | B13 | | | 278-299 | |
| 204R | 24 | | PL ID | 0-0 | 23-21-11 | D00441B | | A03 | | D00443B | A13 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 88

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 205B | 24 | PL | IE | 4-0 | 23-21-11 | D00441B | C08 | | | TB0139F | C185 | 2 | | 050-099 | |
| 205B | 24 | PL | IE | 5-0 | 23-21-11 | D00441B | C08 | | | TB0139F | C185 | 2 | | 150-156, 162-166, 275-276 | |
| 205B | 24 | PL | IE | 5-0 | 23-21-11 | D00441B | C08 | | | TB0139Y | C185 | BJ | | 157, 167-199 | |
| 205B | 24 | PL | IE | 4-0 | 23-21-11 | D00441B | C08 | | | TB0139Y | C185 | BJ | | 277 | |
| 205B | 24 | PL | IE | 2-10 | 23-21-11 | D00441B | C08 | | | TB0139Y | C185 | BJ | | 278-299 | |
| 205R | 24 | PL | IE | 0-0 | 23-21-11 | D00441B | B08 | | | TB0139F | A185 | 2 | | 050-099, 150-156, 162-166, 275-276 | |
| 205R | 24 | PL | IE | 0-0 | 23-21-11 | D00441B | B08 | | | TB0139Y | A185 | BJ | | 157, 167-199, 277-299 | |
| 206B | 24 | PL | IF | 4-0 | 23-21-11 | D00441B | B06 | | | D05709J | 2 | | | 050-099, 150-199, 275-277 | |
| 206B | 24 | PL | IF | 3-0 | 23-21-11 | D00441B | B06 | | | D05709J | 2 | | | 278-299 | |
| 206R | 24 | PL | IF | 0-0 | 23-21-11 | D00441B | A06 | | | D05709J | 1 | | | ALL | |
| 214B | 24 | PW | IN | 4-0 | 23-22-12 | D04931P | 2 | | | TB0139G | 130 | 2 | | 050-099, 150-199, 275-277 | |
| 214B | 24 | PW | IN | 2-9 | 23-22-12 | D04931P | 2 | | | TB0139G | 130 | 2 | | 278-299 | |
| 214R | 24 | PW | IN | 0-0 | 23-22-12 | D04931P | 1 | | | TB0139G | 129 | 2 | | ALL | |
| 214Z | | | IN | 0-0 | 23-22-12 | D04931P | 3 | | | GDY0007 | S.. | 2 | | ALL | |
| 215B | 24 | PL | IO | 4-0 | 23-41-11 | D04953P | 15 | | | TB0139F | C105 | 2 | | 050-099, 150-199, 275-277 | |
| 215B | 24 | PL | IO | 2-11 | 23-41-11 | D04953P | 15 | | | TB0139F | C105 | 2 | | 278-299 | |
| 215R | 24 | PL | IO | 0-0 | 23-41-11 | D04953P | 14 | | | TB0139F | A105 | 2 | | ALL | |
| 216B | 24 | PL | IP | 4-0 | 23-51-14 | D00445B | B15 | | | GDY0013 | S.. | 2 | | 050-099 | |
| 216B | 24 | PL | IP | 3-0 | 23-51-14 | D00445B | B15 | | | GDY0013 | S.. | 2 | | 150-199, 275-277 | |
| 216B | 24 | PL | IP | 2-11 | 23-51-14 | D00445B | B15 | | | GDY0013 | S.. | 2 | | 278-299 | |
| 216R | 24 | PL | IP | 0-0 | 23-51-14 | D00445B | A15 | | | TB0139H | 89 | 2 | | ALL | |
| 217B | 24 | PL | IQ | 4-0 | 23-51-14 | D04601P | 13 | | | TB0139H | 87 | 2 | | 050-099, 150-199, 275-277 | |
| 217B | 24 | PL | IQ | 3-2 | 23-51-14 | D04601P | 13 | | | TB0139H | 87 | 2 | | 278-299 | |
| 217R | 24 | PL | IQ | 0-0 | 23-51-14 | D04601P | 12 | | | TB0139H | 85 | 2 | | ALL | |
| 218B | 24 | PL | IR | 4-0 | 23-51-21 | D04603P | 13 | | | TB0139H | 87 | 2 | | 050-099, 150-199, 275-277 | |
| 218B | 24 | PL | IR | 3-5 | 23-51-21 | D04603P | 13 | | | TB0139H | 87 | 2 | | 278-299 | |
| 218R | 24 | PL | IR | 0-0 | 23-51-21 | D04603P | 12 | | | TB0139H | 85 | 2 | | ALL | |
| 220 | 20 | UA | | 1-6 | 31-35-11 | D00447B | | | IT | GDY0009 | S.. | 2 | | ALL | |
| 220B | 24 | PW | IT | 4-0 | 31-35-11 | D04737P | 25 | | | D00447B | K07 | | | 050-099, 150-199, 275-277 | |
| 220B | 24 | PW | IT | 3-2 | 31-35-11 | D04737P | 25 | | | D00447B | K07 | | | 278-299 | |
| 220R | 24 | PW | IT | 0-0 | 31-35-11 | D04737P | 24 | | | D00447B | J07 | | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 89
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 220Z | | | IT | 0-0 | 31-35-11 | D04737P | | 26 | | | D00447B | | | | IT | ALL |
| 221B | 24 | PL | IU | 4-0 | 23-22-12 | D00447A | | D09 | | | TB0139G | 160 | 2 | | | 050-099, 150-199, 275-277 |
| 221B | 24 | PL | IU | 2-8 | 23-22-12 | D00447A | | D09 | | | TB0139G | 160 | 2 | | | 278-299 |
| 221R | 24 | PL | IU | 0-0 | 23-22-12 | D00447A | | C09 | | | TB0139G | 159 | 2 | | | ALL |
| 222B | 24 | PL | IV | 4-0 | 23-21-11 | D00445B | | B13 | | | TB0139G | 160 | 2 | | | 050-099, 150-199, 275-277 |
| 222B | 24 | PL | IV | 3-2 | 23-21-11 | D00445B | | B13 | | | TB0139G | 160 | 2 | | | 278-299 |
| 222R | 24 | PL | IV | 0-0 | 23-21-11 | D00445B | | A13 | | | TB0139G | 159 | 2 | | | ALL |
| 223B | 24 | PL | IW | 4-0 | 23-22-12 | D00445B | | B05 | | | D00447A | B09 | | | | 050-099, 150-199, 275-277 |
| 223B | 24 | PL | IW | 3-2 | 23-22-12 | D00445B | | B05 | | | D00447A | B09 | | | | 278-299 |
| 223R | 24 | PL | IW | 0-0 | 23-22-12 | D00445B | | A05 | | | D00447A | A09 | | | | ALL |
| 224 | 20 | UA | | 1-6 | 23-22-12 | D00445B | | | | | GD00013 | S.. | 2 | | | 050-099 |
| 224 | 20 | UA | | 1-6 | 23-22-12 | D00445B | | | | | GD00013 | S.. | 2 | | | 150-199, 275-299 |
| 224B | 24 | PW | IX | 4-0 | 23-22-12 | D00445B | | B11 | | | D00447A | B07 | | | | 050-099, 150-199, 275-277 |
| 224B | 24 | PW | IX | 3-2 | 23-22-12 | D00445B | | B11 | | | D00447A | B07 | | | | 278-299 |
| 224R | 24 | PW | IX | 0-0 | 23-22-12 | D00445B | | A11 | | | D00447A | A07 | | | | ALL |
| 224Z | | | IX | 0-0 | 23-22-12 | D00445B | | | | | D00447A | DED | | | | 050-099 |
| 224Z | | | IX | 0-0 | 23-22-12 | D00445B | | | | | D00447A | DED | | | | 150-199, 275-299 |
| 226B | 24 | PL | JA | 6-0 | 23-51-11 | D04601P | | 6 | | | TB0139G | 4 | 2 | | | 050-099 |
| 226B | 24 | PL | JA | 5-0 | 23-51-11 | D04601P | | 6 | | | TB0139G | 4 | 2 | | | 150-199, 275-277 |
| 226B | 24 | PL | JA | 6-1 | 23-51-11 | D04601P | | 6 | | | TB0139G | 4 | 2 | | | 278-299 |
| 226R | 24 | PL | JA | 0-0 | 23-51-11 | D04601P | | 5 | | | TB0139F | C003 | 2 | | | ALL |
| 228B | 24 | PL | JC | 4-0 | 23-51-14 | D04601P | | 17 | | | TB0139H | 73 | 2 | | | 050-099 |
| 228B | 24 | PL | JC | 6-0 | 23-51-14 | D04601P | | 17 | | | TB0139H | 73 | 2 | | | 150-199, 275-277 |
| 228B | 24 | PL | JC | 3-8 | 23-51-14 | D04601P | | 17 | | | TB0139H | 73 | 2 | | | 278-299 |
| 228R | 24 | PL | JC | 0-0 | 23-51-14 | D04601P | | 16 | | | TB0139H | 71 | 2 | | | ALL |
| 229B | 24 | PL | JD | 4-0 | 23-51-14 | D04601P | | 9 | | | TB0139H | 81 | 2 | | | 050-099 |
| 229B | 24 | PL | JD | 6-0 | 23-51-14 | D04601P | | 9 | | | TB0139H | 81 | 2 | | | 150-199, 275-277 |
| 229B | 24 | PL | JD | 3-2 | 23-51-14 | D04601P | | 9 | | | TB0139H | 81 | 2 | | | 278-299 |
| 229R | 24 | PL | JD | 0-0 | 23-51-14 | D04601P | | 8 | | | TB0139H | 79 | 2 | | | ALL |
| 230B | 24 | PL | JE | 4-0 | 23-51-14 | D00443B | | B15 | | | GDY0011 | S.. | 2 | | | 050-099 |
| 230B | 24 | PL | JE | 6-0 | 23-51-14 | D00443B | | B15 | | | GDY0011 | S.. | 2 | | | 150-199, 275-277 |
| 230B | 24 | PL | JE | 3-5 | 23-51-14 | D00443B | | B15 | | | GDY0011 | S.. | 2 | | | 278-299 |
| 230R | 24 | PL | JE | 0-0 | 23-51-14 | D00443B | | A15 | | | TB0139H | 75 | 2 | | | ALL |
| 231B | 24 | PL | JF | 4-0 | 23-51-14 | D00439B | | B15 | | | GDY0013 | S.. | 2 | | | 050-099, 150-199, 275-277 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 90

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 231B | 24 | PL | JF | 3-1 | 23-51-14 | D00439B | B15 | | | | GDY0013 | S.. | 2 | | 278-299 |
| 231R | 24 | PL | JF | 0-0 | 23-51-14 | D00439B | A15 | | | | TB0139H | 83 | 2 | | ALL |
| 232B | 24 | PL | JG | 5-0 | 23-51-12 | D04813P | 9 | | | | GDY0007 | S.. | 2 | | 050-099, 150-199, 275-277 |
| 232B | 24 | PL | JG | 3-9 | 23-51-12 | D04813P | 9 | | | | GDY0007 | S.. | 2 | | 278-299 |
| 232R | 24 | PL | JG | 0-0 | 23-51-12 | D04813P | 8 | | | | TB0139G | 29 | 2 | | 050-099, 150-199 |
| 232R | 24 | PL | JG | 0-0 | 23-51-12 | D04813P | 8 | | | | TB0139H | 34 | 2 | | 275-299 |
| 233B | 24 | PL | JH | 4-0 | 23-51-12 | D04737P | 3 | | | | GDY0007 | S.. | 2 | | 050-099 |
| 233B | 24 | PL | JH | 5-0 | 23-51-12 | D04737P | 3 | | | | GDY0007 | S.. | 2 | | 150-199, 275-277 |
| 233B | 24 | PL | JH | 2-10 | 23-51-12 | D04737P | 3 | | | | GDY0007 | S.. | 2 | | 278-299 |
| 233R | 24 | PL | JH | 0-0 | 23-51-12 | D04737P | 1 | | | | TB0139H | 41 | 2 | | ALL |
| 234B | 24 | PL | JI | 4-0 | 23-51-12 | D04737P | 4 | | | | GDY0007 | S.. | 2 | | 050-099 |
| 234B | 24 | PL | JI | 5-0 | 23-51-12 | D04737P | 4 | | | | GDY0007 | S.. | 2 | | 150-199, 275-277 |
| 234B | 24 | PL | JI | 2-10 | 23-51-12 | D04737P | 4 | | | | GDY0007 | S.. | 2 | | 278-299 |
| 234R | 24 | PL | JI | 0-0 | 23-51-12 | D04737P | 2 | | | | TB0139H | 43 | 2 | | ALL |
| 235B | 24 | PL | JJ | 5-0 | 23-51-41 | D04607P | 13 | | | | TB0139H | 87 | 2 | | 050-099 |
| 235B | 24 | PL | JJ | 4-0 | 23-51-41 | D04607P | 13 | | | | TB0139H | 87 | 2 | | 150-199, 275-277 |
| 235B | 24 | PL | JJ | 3-4 | 23-51-41 | D04607P | 13 | | | | TB0139H | 87 | 2 | | 278-299 |
| 235R | 24 | PL | JJ | 0-0 | 23-51-41 | D04607P | 12 | | | | TB0139H | 85 | 2 | | ALL |
| 236B | 24 | PL | JK | 4-0 | 23-51-14 | D05709J | 4 | | | | GDY0011 | S.. | 2 | | 050-099 |
| 236B | 24 | PL | JK | 5-0 | 23-51-14 | D05709J | 4 | | | | GDY0011 | S.. | 2 | | 150-199, 275-277 |
| 236B | 24 | PL | JK | 2-8 | 23-51-14 | D05709J | 4 | | | | GDY0011 | S.. | 2 | | 278-299 |
| 236R | 24 | PL | JK | 0-0 | 23-51-14 | D05709J | 3 | | | | TB0139H | 66 | 2 | | ALL |
| 238B | 24 | PL | JM | 6-0 | 23-51-21 | D04603P | 6 | | | | TB0139G | 14 | 2 | | 050-099, 150-199, 275-277 |
| 238B | 24 | PL | JM | 6-4 | 23-51-21 | D04603P | 6 | | | | TB0139G | 14 | 2 | | 278-299 |
| 238R | 24 | PL | JM | 0-0 | 23-51-21 | D04603P | 5 | | | | TB0139F | C013 | 2 | | ALL |
| 240B | 24 | PL | JO | 5-0 | 23-51-21 | D04603P | 17 | | | | TB0139H | 73 | 2 | | 050-099 |
| 240B | 24 | PL | JO | 6-0 | 23-51-21 | D04603P | 17 | | | | TB0139H | 73 | 2 | | 150-199, 275-277 |
| 240B | 24 | PL | JO | 3-10 | 23-51-21 | D04603P | 17 | | | | TB0139H | 73 | 2 | | 278-299 |
| 240R | 24 | PL | JO | 0-0 | 23-51-21 | D04603P | 16 | | | | TB0139H | 71 | 2 | | ALL |
| 241B | 24 | PL | JP | 4-0 | 23-51-21 | D04603P | 9 | | | | TB0139H | 81 | 2 | | 050-099 |
| 241B | 24 | PL | JP | 6-0 | 23-51-21 | D04603P | 9 | | | | TB0139H | 81 | 2 | | 150-199, 275-277 |
| 241B | 24 | PL | JP | 3-5 | 23-51-21 | D04603P | 9 | | | | TB0139H | 81 | 2 | | 278-299 |
| 241R | 24 | PL | JP | 0-0 | 23-51-21 | D04603P | 8 | | | | TB0139H | 79 | 2 | | ALL |
| 242 | 20 | UA | | 1-6 | 23-12-31 | D00445B | | | FK | | GDX0011 | S.. | 2 | | ALL |
| 242B | 24 | PW | JQ | 5-0 | 23-12-31 | D00445B | B07 | | | | D04931P | 7 | | | 050-099, 150-199, 275-277 |
| 242B | 24 | PW | JQ | 4-0 | 23-12-31 | D00445B | B07 | | | | D04931P | 7 | | | 278-299 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 91
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|-------|------|------|--------|-------------|--|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | | | |
| 242R | 24 | PW | JQ | | 0-0 | 23-12-31 | D00445B | A07 | | | | | | | | 6 | | ALL |
| 242Z | | | JQ | | 0-0 | 23-12-31 | D00445B | | | | | | | | | | | ALL |
| 243B | 24 | PL | JR | | 7-0 | 23-51-41 | D04607P | | | | | | | | | | | 050-099 |
| 243B | 24 | PL | JR | | 6-0 | 23-51-41 | D04607P | | | | | | | | | | | 150-199, 275-277 |
| 243B | 24 | PL | JR | | 6-3 | 23-51-41 | D04607P | | | | | | | | | | | 278-299 |
| 243R | 24 | PL | JR | | 0-0 | 23-51-41 | D04607P | | | | | | | | | | | ALL |
| 246B | 24 | PL | JU | | 5-0 | 23-51-41 | D04607P | | | | | | | | | | | 050-099 |
| 246B | 24 | PL | JU | | 4-0 | 23-51-41 | D04607P | | | | | | | | | | | 150-199, 275-277 |
| 246B | 24 | PL | JU | | 3-10 | 23-51-41 | D04607P | | | | | | | | | | | 278-299 |
| 246R | 24 | PL | JU | | 0-0 | 23-51-41 | D04607P | | | | | | | | | | | ALL |
| 247B | 24 | PL | JV | | 4-0 | 23-51-41 | D04607P | | | | | | | | | | | 050-099, 150-199, 275-277 |
| 247B | 24 | PL | JV | | 3-4 | 23-51-41 | D04607P | | | | | | | | | | | 278-299 |
| 247R | 24 | PL | JV | | 0-0 | 23-51-41 | D04607P | | | | | | | | | | | ALL |
| 248B | 24 | PL | JW | | 4-0 | 23-21-11 | D00441B | B05 | | | | | | | | | | 050-099, 150-199 |
| 248B | 24 | PL | JW | | 5-0 | 23-21-11 | D00441B | B05 | | | | | | | | | | 275-277 |
| 248B | 24 | PL | JW | | 3-8 | 23-21-11 | D00441B | B05 | | | | | | | | | | 278-299 |
| 248R | 24 | PL | JW | | 0-0 | 23-21-11 | D00441B | A05 | | | | | | | | | | ALL |
| 254B | 24 | PL | KD | | 4-0 | 23-51-13 | D04737P | | | | | | | | | | | 050-099, 150-199, 275-277 |
| 254B | 24 | PL | KD | | 3-3 | 23-51-13 | D04737P | | | | | | | | | | | 278-299 |
| 254R | 24 | PL | KD | | 0-0 | 23-51-13 | D04737P | | | | | | | | | | | ALL |
| 255B | 24 | PL | KE | | 5-0 | 23-51-13 | D04813P | | | | | | | | | | | 050-099, 150-199, 275-277 |
| 255B | 24 | PL | KE | | 3-8 | 23-51-13 | D04813P | | | | | | | | | | | 278-299 |
| 255R | 24 | PL | KE | | 0-0 | 23-51-13 | D04813P | | | | | | | | | | | ALL |
| 256B | 24 | PL | KF | | 3-0 | 23-51-13 | D04737P | | | | | | | | | | | 050-099 |
| 256B | 24 | PL | KF | | 4-0 | 23-51-13 | D04737P | | | | | | | | | | | 150-199, 275-277 |
| 256B | 24 | PL | KF | | 2-10 | 23-51-13 | D04737P | | | | | | | | | | | 278-299 |
| 256R | 24 | PL | KF | | 0-0 | 23-51-13 | D04737P | | | | | | | | | | | ALL |
| 257B | 22 | PB | KG | | 5-0 | 23-22-11 | TB0139G | | | | | | | | | | | 050-099 |
| 257B | 22 | PB | KG | | 5-0 | 23-22-11 | D04213P | | | | | | | | | | | 150-199, 275-277 |
| 257B | 22 | PB | KG | | 4-0 | 23-22-11 | D04213P | | | | | | | | | | | 278-299 |
| 257R | 22 | PB | KG | | 0-0 | 23-22-11 | TB0139G | | | | | | | | | | | 050-099 |
| 257R | 22 | PB | KG | | 0-0 | 23-22-11 | D04213P | | | | | | | | | | | 150-199, 275-299 |
| 260 | 20 | UA | | | 3-0 | 34-61-15 | D00447B | | | | | | | | | | | 150-199, 275-277 |
| 260 | 20 | UA | | | 2-2 | 34-61-15 | D00447B | | | | | | | | | | | 278-299 |
| 260B | 24 | PW | KJ | | 4-0 | 34-61-15 | D00447B | | | | | | | | | | | 150-199, 275-277 |
| 260B | 24 | PW | KJ | | 3-2 | 34-61-15 | D00447B | | | | | | | | | | | 278-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 92

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|----------|---------|---------|-------|------|------|---------|-------|------|------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 260R | 24 | PW | KJ | 0-0 | 34-61-15 | D00447B | | G13 | | | D04737P | 8 | | | 150-199, 275-299 |
| 260Z | | | KJ | 0-0 | 34-61-15 | D00447B | | | | FQ | D04737P | 23 | | | 150-199, 275-299 |
| 262 | 20 | UA | | 1-6 | 34-61-25 | D00447B | | | | KL | GDX0009 | S.. | 2 | | ALL |
| 262B | 24 | PW | KL | 4-0 | 34-61-25 | D04813P | | 33 | | | D00447B | K13 | | | 050-099, 150-199, 275-277 |
| 262B | 24 | PW | KL | 3-2 | 34-61-25 | D04813P | | 33 | | | D00447B | K13 | | | 278-299 |
| 262R | 24 | PW | KL | 0-0 | 34-61-25 | D04813P | | 32 | | | D00447B | J13 | | | ALL |
| 262Z | | | KL | 0-0 | 34-61-25 | D04813P | | 34 | | | D00447B | | | KL | ALL |
| 269B | 22 | PB | KS | 4-0 | 23-22-11 | TB0139G | | 148 | 2 | | D00447C | 7 | | | 050-099 |
| 269B | 22 | PB | KS | 4-0 | 23-22-11 | D00447C | | 7 | | | TB0139G | 148 | 2 | | 150-199, 275-277 |
| 269B | 22 | PB | KS | 3-0 | 23-22-11 | D00447C | | 7 | | | TB0139G | 148 | 2 | | 278-299 |
| 269R | 22 | PB | KS | 0-0 | 23-22-11 | TB0139G | | 147 | 2 | | D00447C | 1 | | | 050-099 |
| 269R | 22 | PB | KS | 0-0 | 23-22-11 | D00447C | | 1 | | | TB0139G | 147 | 2 | | 150-199, 275-299 |
| 270B | 24 | PW | KT | 4-0 | 23-22-12 | D04737P | | 28 | | | TB0139G | 132 | 2 | | 050-099 |
| 270B | 24 | PW | GA | 4-0 | 23-22-12 | TB0139G | | 132 | 2 | | D04737P | 28 | | | 150-199, 275-277 |
| 270B | 24 | PW | GA | 2-6 | 23-22-12 | TB0139G | | 132 | 2 | | D04737P | 28 | | | 278-299 |
| 270R | 24 | PW | KT | 0-0 | 23-22-12 | D04737P | | 27 | | | TB0139G | 131 | 2 | | 050-099 |
| 270R | 24 | PW | GA | 0-0 | 23-22-12 | TB0139G | | 131 | 2 | | D04737P | 27 | | | 150-199, 275-299 |
| 270Z | | | KT | 0-0 | 23-22-12 | D04737P | | 29 | | | GDY0007 | S.. | 2 | | 050-099 |
| 270Z | | | GA | 0-0 | 23-22-12 | GDY0007 | | S.. | 2 | | D04737P | 29 | | | 150-199, 275-299 |
| 271 | 20 | UA | | 4-0 | 23-22-12 | D00447B | | | | KU | GDX0013 | S.. | E | | 050-099 |
| 271 | 20 | UA | | 4-0 | 23-22-12 | D00447B | | | | FM | GDX0013 | S.. | 2 | | 150-199, 275-277 |
| 271 | 20 | UA | | 2-10 | 23-22-12 | D00447B | | | | FM | GDX0013 | S.. | 2 | | 278 |
| 271B | 24 | PW | KU | 4-0 | 23-22-12 | D00447B | | D12 | | | TB0139F | C149 | 2 | | 050-099 |
| 271B | 24 | PW | GB | 4-0 | 23-22-12 | D00447B | | D12 | | | TB0139F | C149 | 2 | | 150-199, 275-277 |
| 271B | 24 | PW | GB | 3-0 | 23-22-12 | D00447B | | D12 | | | TB0139F | C149 | 2 | | 278 |
| 271R | 24 | PW | KU | 0-0 | 23-22-12 | D00447B | | C12 | | | TB0139F | A149 | 2 | | 050-099 |
| 271R | 24 | PW | GB | 0-0 | 23-22-12 | D00447B | | C12 | | | TB0139F | A149 | 2 | | 150-199, 275-278 |
| 271Z | | | KU | 0-0 | 23-22-12 | D00447B | | | | KU | TB0139F | A151 | 2 | | 050-099 |
| 271Z | | | GB | 0-0 | 23-22-12 | D00447B | | | | FM | TB0139F | A151 | 2 | | 150-199, 275-278 |
| 272 | 20 | UA | | 4-0 | 23-22-12 | D00447B | | | | KV | GDX0013 | S.. | E | | 050-099 |
| 272 | 20 | UA | | 4-0 | 23-22-12 | D00447B | | | | FN | GDX0013 | S.. | 2 | | 150-199, 275-277 |
| 272 | 20 | UA | | 2-10 | 23-22-12 | D00447B | | | | FN | GDX0013 | S.. | 2 | | 278 |
| 272B | 24 | PW | KV | 4-0 | 23-22-12 | D00447B | | F12 | | | TB0139F | C150 | 2 | | 050-099 |
| 272B | 24 | PW | GC | 4-0 | 23-22-12 | D00447B | | F12 | | | TB0139F | C150 | 2 | | 150-199 |
| 272B | 24 | PW | GC | 4-0 | 23-22-12 | D00447B | | F12 | | | TB0139F | C157 | 2 | | 275-277 |
| 272B | 24 | PW | GC | 2-8 | 23-22-12 | D00447B | | F12 | | | TB0139F | C157 | 2 | | 278 |
| 272R | 24 | PW | KV | 0-0 | 23-22-12 | D00447B | | E12 | | | TB0139F | A150 | 2 | | 050-099 |
| 272R | 24 | PW | GC | 0-0 | 23-22-12 | D00447B | | E12 | | | TB0139F | A150 | 2 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 93

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|----------|---------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 272R | 24 | PW | GC | 0-0 | 23-22-12 | D00447B | | E12 | | | | | | | | 275-278 |
| 272Z | | | KV | 0-0 | 23-22-12 | D00447B | | | | | KV | TB0139F | A157 | 2 | | 050-099 |
| 272Z | | | GC | 0-0 | 23-22-12 | D00447B | | | | | FN | TB0139F | C151 | 2 | | 150-199 |
| 272Z | | | GC | 0-0 | 23-22-12 | D00447B | | | | | FN | TB0139F | C156 | 2 | | 275-278 |
| 280B | 24 | PW | LE | 4-0 | 31-35-13 | D04737P | | 34 | | | | TB0139F | C035 | 2 | | 050-099 |
| 280B | 24 | PW | LE | 4-0 | 31-35-13 | TB0139F | | | C035 | 2 | | D04737P | 34 | | | 150-199 |
| 280B | 24 | PW | LE | 4-0 | 31-35-13 | TB0139F | | | C033 | 2 | | D04737P | 34 | | | 275-277 |
| 280B | 24 | PW | LE | 2-7 | 31-35-13 | TB0139F | | | C033 | 2 | | D04737P | 34 | | | 278-299 |
| 280R | 24 | PW | LE | 0-0 | 31-35-13 | D04737P | | | 33 | | | TB0139F | A035 | 2 | | 050-099 |
| 280R | 24 | PW | LE | 0-0 | 31-35-13 | TB0139F | | | A035 | 2 | | D04737P | 33 | | | 150-199 |
| 280R | 24 | PW | LE | 0-0 | 31-35-13 | TB0139F | | | A033 | 2 | | D04737P | 33 | | | 275-299 |
| 280Z | | | LE | 0-0 | 31-35-13 | D04737P | | | 35 | | | GDY0007 | S.. | 2 | | 050-099 |
| 280Z | | | LE | 0-0 | 31-35-13 | GDY0007 | | | S.. | 2 | | D04737P | 35 | | | 150-199, 275-299 |
| 281 | 20 | UA | | 2-0 | 31-36-11 | D00447B | | | | | LF | GDY0007 | S.. | 2 | | 050-099 |
| 281 | 20 | UA | | 4-0 | 31-36-11 | D00447B | | | | | LF | GDY0007 | S.. | 2 | | 150-199, 275-277 |
| 281 | 20 | UA | | 2-4 | 31-36-11 | D00447B | | | | | LF | GDY0007 | S.. | 2 | | 278-299 |
| 281B | 24 | PW | LF | 4-0 | 31-36-11 | D04737P | | | 31 | | | D00447B | K12 | | | 050-099 |
| 281B | 24 | PW | LF | 4-0 | 31-36-11 | D00447B | | | K12 | | | D04737P | 31 | | | 150-199, 275-277 |
| 281B | 24 | PW | LF | 3-2 | 31-36-11 | D00447B | | | K12 | | | D04737P | 31 | | | 278-299 |
| 281R | 24 | PW | LF | 0-0 | 31-36-11 | D04737P | | | 30 | | | D00447B | J12 | | | 050-099 |
| 281R | 24 | PW | LF | 0-0 | 31-36-11 | D00447B | | | J12 | | | D04737P | 30 | | | 150-199, 275-299 |
| 281Z | | | LF | 0-0 | 31-36-11 | D04737P | | | 32 | | | D00447B | | | LF | 050-099 |
| 281Z | | | LF | 0-0 | 31-36-11 | D00447B | | | | | LF | D04737P | 32 | | | 150-199, 275-299 |
| 282B | 24 | PW | LG | 4-0 | 23-22-12 | D00447B | | | F15 | | | TB0139G | 130 | 2 | | 050-099, 150-199, 275-277 |
| 282B | 24 | PW | LG | 3-2 | 23-22-12 | D00447B | | | F15 | | | TB0139G | 130 | 2 | | 278-299 |
| 282R | 24 | PW | LG | 0-0 | 23-22-12 | D00447B | | | E15 | | | TB0139G | 129 | 2 | | ALL |
| 282Z | | | LG | 0-0 | 23-22-12 | D00447B | | | DED | | | GDY0007 | S.. | 2 | | ALL |
| 283B | 24 | PW | LH | 4-0 | 23-22-12 | D00447B | | | H15 | | | TB0139G | 132 | 2 | | 050-099, 150-199, 275-277 |
| 283B | 24 | PW | LH | 3-2 | 23-22-12 | D00447B | | | H15 | | | TB0139G | 132 | 2 | | 278-299 |
| 283R | 24 | PW | LH | 0-0 | 23-22-12 | D00447B | | | G15 | | | TB0139G | 131 | 2 | | ALL |
| 283Z | | | LH | 0-0 | 23-22-12 | D00447B | | | DED | | | GDY0007 | S.. | 2 | | ALL |
| 284B | 24 | PW | LI | 4-0 | 23-22-12 | D04813P | | | 11 | | | TB0139G | 132 | 2 | | 050-099 |
| 284B | 24 | PW | LI | 5-0 | 23-22-12 | D04813P | | | 11 | | | TB0139G | 132 | 2 | | 150-199, 275-277 |
| 284B | 24 | PW | LI | 3-8 | 23-22-12 | D04813P | | | 11 | | | TB0139G | 132 | 2 | | 278-299 |
| 284R | 24 | PW | LI | 0-0 | 23-22-12 | D04813P | | | 10 | | | TB0139G | 131 | 2 | | ALL |
| 284Z | | | LI | 0-0 | 23-22-12 | D04813P | | | 12 | | | GDY0007 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 94

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 285B | 24 | PW | LJ | 4-0 | 23-22-12 | D04737P | 11 | | | TB0139G | 130 | 2 | | 050-099, 150-199, 275-277 | |
| 285B | 24 | PW | LJ | 2-6 | 23-22-12 | D04737P | 11 | | | TB0139G | 130 | 2 | | 278-299 | |
| 285R | 24 | PW | LJ | 0-0 | 23-22-12 | D04737P | 10 | | | TB0139G | 129 | 2 | | ALL | |
| 285Z | | | LJ | 0-0 | 23-22-12 | D04737P | 12 | | | GDY0007 | S.. | 2 | | ALL | |
| 286B | 24 | PW | LK | 5-0 | 23-22-12 | D04813P | 36 | | | TB0139G | 132 | 2 | | 050-099, 150-199, 275-277 | |
| 286B | 24 | PW | LK | 3-8 | 23-22-12 | D04813P | 36 | | | TB0139G | 132 | 2 | | 278-299 | |
| 286R | 24 | PW | LK | 0-0 | 23-22-12 | D04813P | 35 | | | TB0139G | 131 | 2 | | ALL | |
| 286Z | | | LK | 0-0 | 23-22-12 | D04813P | 37 | | | GDY0007 | S.. | 2 | | ALL | |
| 287 | 20 | UA | | 3-0 | 23-22-11 | D00447B | | | LL | GDY0007 | S.. | 2 | | 050-099, 150-199, 275-277 | |
| 287 | 20 | UA | | 2-5 | 23-22-11 | D00447B | | | LL | GDY0007 | S.. | 2 | | 278-299 | |
| 287B | 24 | PW | LL | 4-0 | 23-22-11 | D00447B | B14 | | | D04737P | 19 | | | 050-099 | |
| 287B | 24 | PW | LL | 4-0 | 23-22-11 | D04737P | 19 | | | D00447B | B14 | | | 150-199, 275-277 | |
| 287B | 24 | PW | LL | 3-2 | 23-22-11 | D04737P | 19 | | | D00447B | B14 | | | 278-299 | |
| 287R | 24 | PW | LL | 0-0 | 23-22-11 | D00447B | A14 | | | D04737P | 18 | | | 050-099 | |
| 287R | 24 | PW | LL | 0-0 | 23-22-11 | D04737P | 18 | | | D00447B | A14 | | | 150-199, 275-299 | |
| 287Z | | | LL | 0-0 | 23-22-11 | D00447B | | | LL | D04737P | 20 | | | 050-099 | |
| 287Z | | | LL | 0-0 | 23-22-11 | D04737P | 20 | | | D00447B | | | LL | 150-199, 275-299 | |
| 288 | 20 | UA | | 4-0 | 23-22-11 | D00447B | | | LM | GDY0005 | S.. | 2 | | 050-099, 150-199, 275-277 | |
| 288 | 20 | UA | | 2-10 | 23-22-11 | D00447B | | | LM | GDY0005 | S.. | 2 | | 278-299 | |
| 288B | 24 | PW | LM | 4-0 | 23-22-11 | D00447B | D14 | | | D04813P | 39 | | | 050-099 | |
| 288B | 24 | PW | LM | 4-0 | 23-22-11 | D04813P | 39 | | | D00447B | D14 | | | 150-199, 275-277 | |
| 288B | 24 | PW | LM | 3-2 | 23-22-11 | D04813P | 39 | | | D00447B | D14 | | | 278-299 | |
| 288R | 24 | PW | LM | 0-0 | 23-22-11 | D00447B | C14 | | | D04813P | 38 | | | 050-099 | |
| 288R | 24 | PW | LM | 0-0 | 23-22-11 | D04813P | 38 | | | D00447B | C14 | | | 150-199, 275-299 | |
| 288Z | | | LM | 0-0 | 23-22-11 | D00447B | | | LM | D04813P | 40 | | | 050-099 | |
| 288Z | | | LM | 0-0 | 23-22-11 | D04813P | 40 | | | D00447B | | | LM | 150-199, 275-299 | |
| 289 | 20 | UA | | 4-0 | 23-22-11 | D00447B | | | LN | GDY0005 | S.. | 2 | | 050-099, 150-199, 275-277 | |
| 289 | 20 | UA | | 2-10 | 23-22-11 | D00447B | | | LN | GDY0005 | S.. | 2 | | 278-299 | |
| 289B | 24 | PW | LN | 4-0 | 23-22-11 | D00447B | F14 | | | D04813P | 26 | | | 050-099 | |
| 289B | 24 | PW | LN | 4-0 | 23-22-11 | D04813P | 26 | | | D00447B | F14 | | | 150-199, 275-277 | |
| 289B | 24 | PW | LN | 3-2 | 23-22-11 | D04813P | 26 | | | D00447B | F14 | | | 278-299 | |
| 289R | 24 | PW | LN | 0-0 | 23-22-11 | D00447B | E14 | | | D04813P | 25 | | | 050-099 | |
| 289R | 24 | PW | LN | 0-0 | 23-22-11 | D04813P | 25 | | | D00447B | E14 | | | 150-199, 275-299 | |
| 289Z | | | LN | 0-0 | 23-22-11 | D00447B | | | LN | D04813P | 27 | | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 95

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 289Z | | | LN | 0-0 | 23-22-11 | D04813P | | 27 | | | D00447B | | | LN | 150-199, 275-299 |
| 302B | 24 | PM | MB | 4-0 | 23-51-14 | D00443B | | B01 | | | GDY0011 | S.. | 2 | | 050-099 |
| 302B | 24 | PM | MB | 6-0 | 23-51-14 | D00443B | | B01 | | | GDY0011 | S.. | 2 | | 150-199, 275-277 |
| 302B | 24 | PM | MB | 3-5 | 23-51-14 | D00443B | | B01 | | | GDY0011 | S.. | 2 | | 278-299 |
| 302R | 24 | PM | MB | 0-0 | 23-51-14 | D00443B | | A01 | | | TB0139H | 71 | 2 | | ALL |
| 302Y | 24 | PM | MB | 0-0 | 23-51-14 | D00443B | | C01 | | | TB0139H | 73 | 2 | | ALL |
| 303B | 24 | PM | MC | 4-0 | 23-51-14 | D00439B | | B01 | | | GDY0013 | S.. | 2 | | 050-099, 150-199, 275-277 |
| 303B | 24 | PM | MC | 3-1 | 23-51-14 | D00439B | | B01 | | | GDY0013 | S.. | 2 | | 278-299 |
| 303R | 24 | PM | MC | 0-0 | 23-51-14 | D00439B | | A01 | | | TB0139H | 79 | 2 | | ALL |
| 303Y | 24 | PM | MC | 0-0 | 23-51-14 | D00439B | | C01 | | | TB0139H | 81 | 2 | | ALL |
| 304B | 24 | PM | MD | 5-0 | 23-51-12 | D04813P | | 7 | | | GDY0007 | S.. | 2 | | 050-099, 150-199, 275-277 |
| 304B | 24 | PM | MD | 3-9 | 23-51-12 | D04813P | | 7 | | | GDY0007 | S.. | 2 | | 278-299 |
| 304R | 24 | PM | MD | 0-0 | 23-51-12 | D04813P | | 5 | | | TB0139Z | 27 | BJ | | 050-099, 150-199 |
| 304R | 24 | PM | MD | 0-0 | 23-51-12 | D04813P | | 5 | | | TB0139H | 29 | 2 | | 275-299 |
| 304Y | 24 | PM | MD | 0-0 | 23-51-12 | D04813P | | 6 | | | TB0139G | 28 | 2 | | 050-099, 150-199 |
| 304Y | 24 | PM | MD | 0-0 | 23-51-12 | D04813P | | 6 | | | TB0139H | 31 | 2 | | 275-299 |
| 305B | 24 | PM | ME | 4-0 | 23-51-12 | D04737P | | 7 | | | GDY0007 | S.. | 2 | | 050-099 |
| 305B | 24 | PM | ME | 5-0 | 23-51-12 | D04737P | | 7 | | | GDY0007 | S.. | 2 | | 150-199, 275-277 |
| 305B | 24 | PM | ME | 2-10 | 23-51-12 | D04737P | | 7 | | | GDY0007 | S.. | 2 | | 278-299 |
| 305R | 24 | PM | ME | 0-0 | 23-51-12 | D04737P | | 5 | | | TB0139H | 36 | 2 | | ALL |
| 305Y | 24 | PM | ME | 0-0 | 23-51-12 | D04737P | | 6 | | | TB0139H | 38 | 2 | | ALL |
| 306B | 24 | PM | MF | 4-0 | 23-51-14 | D05709J | | 6 | | | GDY0009 | S.. | 2 | | 050-099 |
| 306B | 24 | PM | MF | 5-0 | 23-51-14 | D05709J | | 6 | | | GDY0009 | S.. | 2 | | 150-199, 275-277 |
| 306B | 24 | PM | MF | 3-1 | 23-51-14 | D05709J | | 6 | | | GDY0009 | S.. | 2 | | 278-299 |
| 306R | 24 | PM | MF | 0-0 | 23-51-14 | D05709J | | 5 | | | TB0139H | 62 | 2 | | ALL |
| 306Y | 24 | PM | MF | 0-0 | 23-51-14 | D05709J | | 7 | | | TB0139H | 64 | 2 | | ALL |
| 307B | 24 | PM | MG | 4-0 | 23-51-14 | D00445B | | B01 | | | GDY0013 | S.. | 2 | | 050-099, 150-199, 275-277 |
| 307B | 24 | PM | MG | 2-11 | 23-51-14 | D00445B | | B01 | | | GDY0013 | S.. | 2 | | 278-299 |
| 307R | 24 | PM | MG | 0-0 | 23-51-14 | D00445B | | A01 | | | TB0139H | 85 | 2 | | ALL |
| 307Y | 24 | PM | MG | 0-0 | 23-51-14 | D00445B | | C01 | | | TB0139H | 87 | 2 | | ALL |
| 401B | 24 | PY | QA | 6-0 | 23-42-11 | D04927P | | 3 | | | TB0139F | C142 | 2 | | 050-099 |
| 401B | 24 | PY | QA | 7-0 | 23-42-11 | D04927P | | 3 | | | TB0139F | C142 | 2 | | 150-199, 275-277 |
| 401B | 24 | PY | QA | 4-7 | 23-42-11 | D04927P | | 3 | | | TB0139F | C142 | 2 | | 278-299 |
| 401G | 24 | PY | QA | 0-0 | 23-42-11 | D04927P | | 5 | | | TB0139F | C143 | 2 | | ALL |
| 401R | 24 | PY | QA | 0-0 | 23-42-11 | D04927P | | 1 | | | TB0139F | A142 | 2 | | ALL |
| 401Y | 24 | PY | QA | 0-0 | 23-42-11 | D04927P | | 11 | | | TB0139F | A143 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 96

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 401Z | | | | QA | 0-0 | 23-42-11 | D04927P | | | | TB0139F | C144 | 2 | | ALL |
| 551 | 24 | | PK | | 5-0 | 23-51-41 | D04953P | | | | TB0139D | C154 | 2 | | 050-099 |
| 551 | 24 | | PK | | 4-0 | 23-51-41 | D04953P | | | | TB0139D | C154 | 2 | | 150-152 |
| 551 | 24 | | PK | | 0-6 | 23-51-41 | D04953P | | | | TB0139D | C154 | 2 | | 153-199, 275-277 |
| 551 | 24 | | PK | | 4-6 | 23-51-41 | D04953P | | | | TB0139D | C154 | 2 | | 278-299 |
| 552 | 24 | | PK | | 7-0 | 23-51-11 | D04601P | | | 18 | TB0139Z | | 9 | BJ | 150-152 |
| 553 | 20 | | PQ | WC | 4-0 | 23-22-11 | TB0139G | | 162 | 2 | D00447C | | 10 | | 277 |
| 553 | 20 | | PQ | WC | 2-9 | 23-22-11 | TB0139G | | 162 | 2 | D00447C | | 10 | | 278 |
| 553 | 20 | | PQ | C | 5-0 | 23-22-11 | TB0139G | | 162 | 2 | D00447C | | 10 | | 280-299 |
| 553Z | | | | WC | 0-0 | 23-22-11 | TB0139G | | | DED | D00447C | | DED | | 277-278 |
| 553Z | | | | C | 0-0 | 23-22-11 | TB0139G | | | DED | D00447C | | DED | | 280-299 |
| 554 | 24 | | PK | | 5-0 | 23-51-11 | D04929P | | | 12 | TB0139D | C152 | 2 | | 050-099, 153-199, 275-277 |
| 554 | 24 | | PK | | 7-0 | 23-51-11 | D04929P | | | 12 | TB0139D | C152 | 2 | | 150-152 |
| 554 | 24 | | PK | | 3-10 | 23-51-11 | D04929P | | | 12 | TB0139D | C152 | 2 | | 278-299 |
| 577 | 24 | | PK | | 4-0 | 23-22-12 | D00447A | | | G14 | TB0139H | | 77 | 2 | 050-099 |
| 577 | 24 | | PK | | 4-0 | 23-22-12 | TB0139Z | | 78 | BJ | D00447A | G14 | | | 150-199, 275-277 |
| 577 | 24 | | PK | | 3-4 | 23-22-12 | TB0139Z | | 78 | BJ | D00447A | G14 | | | 278-299 |
| 578 | 24 | | PK | | 4-0 | 23-22-12 | D00447A | | A14 | | TB0139H | | 77 | 2 | 050-099 |
| 578 | 24 | | PK | | 4-0 | 23-22-12 | TB0139Z | | 77 | BJ | D00447A | A14 | | | 150-199, 275-277 |
| 578 | 24 | | PK | | 3-4 | 23-22-12 | TB0139Z | | 77 | BJ | D00447A | A14 | | | 278-299 |
| 579 | 24 | | PK | | 4-0 | 23-22-12 | D00447A | | B14 | | TB0139H | | 77 | 2 | 050-099 |
| 579 | 24 | | PK | | 4-0 | 23-22-12 | TB0139Z | | 77 | BJ | D00447A | B14 | | | 150-199, 275-277 |
| 579 | 24 | | PK | | 3-4 | 23-22-12 | TB0139Z | | 77 | BJ | D00447A | B14 | | | 278-299 |
| 581 | 24 | | PK | | 4-0 | 23-22-12 | D00447A | | D14 | | TB0139H | | 77 | 2 | 050-099 |
| 581 | 24 | | PK | | 4-0 | 23-22-12 | TB0139Z | | 77 | BJ | D00447A | D14 | | | 150-199, 275-277 |
| 581 | 24 | | PK | | 3-4 | 23-22-12 | TB0139Z | | 77 | BJ | D00447A | D14 | | | 278-299 |
| 586 | 24 | | PK | | 4-0 | 23-22-12 | D00447A | | D07 | | TB0139H | | 77 | 2 | 050-099 |
| 586 | 24 | | PK | | 4-0 | 23-22-12 | TB0139Z | | 78 | BJ | D00447A | D07 | | | 150-199, 275-277 |
| 586 | 24 | | PK | | 3-4 | 23-22-12 | TB0139Z | | 78 | BJ | D00447A | D07 | | | 278-299 |
| 587 | 22 | | PA | | 3-0 | 23-22-11 | D00447B | | G09 | | GDX0009 | S.. | 2 | | 150, 152-199, 277 |
| 587 | 22 | | PA | | 2-2 | 23-22-11 | D00447B | | G09 | | GDX0009 | S.. | 2 | | 278 |
| 617 | 24 | | PK | | 4-0 | 23-22-12 | D00447A | | C14 | | TB0139H | | 77 | 2 | 050-099 |
| 617 | 24 | | PK | | 4-0 | 23-22-12 | TB0139Z | | 77 | BJ | D00447A | C14 | | | 150-199, 275-277 |
| 617 | 24 | | PK | | 3-4 | 23-22-12 | TB0139Z | | 77 | BJ | D00447A | C14 | | | 278-299 |
| 626 | 22 | | PA | | 4-0 | 23-24-11 | D05001P | | 31 | | TB0139F | A196 | 2 | | 050-099 |
| 626 | 22 | | PA | | 3-0 | 23-24-11 | D05001P | | 31 | | TB0139X | A196 | BJ | | 150-199 |
| 627 | 22 | | PA | | 4-0 | 23-24-11 | D05001P | | 32 | | TB0139F | C196 | 2 | | 050-099 |
| 627 | 22 | | PA | | 3-0 | 23-24-11 | D05001P | | 32 | | TB0139X | B196 | BJ | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 97
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | | |
| 633 | 24 | | PK | | 4-0 | 23-22-11 | D00447B | | F09 | | | | TB0139G | 166 | 2 | | 277 |
| 633 | 24 | | PK | | 2-9 | 23-22-11 | D00447B | | F09 | | | | TB0139G | 166 | 2 | | 278 |
| 637 | 24 | | PK | | 5-0 | 23-22-12 | D00447A | | C07 | | | | TB0139D | C166 | 2 | | 167-199 |
| 650 | 22 | | PQ | ZY | 6-0 | 23-42-11 | D05001P | | 9 | | | | TB0139H | 111 | 2 | | 050-099 |
| 650 | 22 | | PQ | ZY | 6-0 | 23-42-11 | D05001P | | 9 | | | | TB0139Z | 122 | BJ | | 162-199 |
| 650Z | | | | ZY | 0-0 | 23-42-11 | D05001P | | DED | | | | TB0139H | DED | | | 050-099 |
| 650Z | | | | ZY | 0-0 | 23-42-11 | D05001P | | DED | | | | TB0139Z | DED | | | 162-199 |
| 651 | 22 | | PA | | 5-0 | 23-42-11 | D05001P | | 38 | | | | TB0139F | A156 | 2 | | 050-099 |
| 651 | 22 | | PA | | 4-0 | 23-42-11 | D05001P | | 38 | | | | TB0139F | A162 | 2 | | 162-199 |
| 652 | 22 | | PA | | 5-0 | 23-42-11 | D05001P | | 39 | | | | TB0139F | C156 | 2 | | 050-099 |
| 652 | 22 | | PA | | 4-0 | 23-42-11 | D05001P | | 39 | | | | TB0139F | C162 | 2 | | 162-199 |
| 653 | 22 | | PA | | 6-0 | 23-42-11 | D05001P | | 40 | | | | TB0139F | A120 | 2 | | 050-099, 162-199 |
| 654 | 24 | | PK | | 6-0 | 23-22-15 | D00447A | | E06 | | | | D04953P | 8 | | | 050-099, 155-199 |
| 654 | 24 | | PK | | 15-0 | 23-22-15 | D00447A | | E06 | | | | D04953P | 8 | | | 150-154 |
| 654 | 24 | | PK | | 9-0 | 23-22-15 | D00447A | | E06 | | | | D04953P | 8 | | | 275-277 |
| 654 | 24 | | PK | | 4-9 | 23-22-15 | D00447A | | E06 | | | | D04953P | 8 | | | 278-299 |
| 655 | 24 | | PK | | 5-0 | 23-51-11 | TB0139Z | | 10 | BJ | | | TB0139D | A152 | 2 | | 050-099, 150-199 |
| 655 | 24 | | PK | | 5-0 | 23-51-11 | TB0139H | | 9 | 2 | | | TB0139D | A152 | 2 | | 275-277 |
| 655 | 24 | | PK | | 4-2 | 23-51-11 | TB0139H | | 9 | 2 | | | TB0139D | A152 | 2 | | 278-299 |
| 657 | 20 | | UA | | 4-0 | 23-22-15 | D00447A | | | | A7 | | GDX0011 | S.. | 2 | | 050-099 |
| 657 | 20 | | PA | | 8-0 | 23-22-15 | D00447A | | | | A7 | | GDX0011 | S.. | 2 | | 150-154 |
| 657 | 20 | | PA | | 3-0 | 23-22-15 | D00447A | | | | A7 | | GDX0011 | S.. | 2 | | 155-199, 275-277 |
| 657 | 20 | | PA | | 2-4 | 23-22-15 | D00447A | | | | A7 | | GDX0011 | S.. | 2 | | 278-299 |
| 657B | 24 | | PW | A7 | 6-0 | 23-22-15 | D00447A | | G06 | | | | D04953P | 7 | | | 050-099, 155-199 |
| 657B | 24 | | PW | A7 | 15-0 | 23-22-15 | D00447A | | G06 | | | | D04953P | 7 | | | 150-154 |
| 657B | 24 | | PW | A7 | 9-0 | 23-22-15 | D00447A | | G06 | | | | D04953P | 7 | | | 275-277 |
| 657B | 24 | | PW | A7 | 4-9 | 23-22-15 | D00447A | | G06 | | | | D04953P | 7 | | | 278-299 |
| 657R | 24 | | PW | A7 | 0-0 | 23-22-15 | D00447A | | F06 | | | | D04953P | 6 | | | ALL |
| 657Z | | | | A7 | 0-0 | 23-22-15 | D00447A | | | | A7 | | D04953P | 9 | | | ALL |
| 658 | 20 | | UA | | 4-0 | 23-22-15 | D00447A | | | | A8 | | GDX0011 | S.. | 2 | | 050-099 |
| 658 | 20 | | PA | | 8-0 | 23-22-15 | D00447A | | | | A8 | | GDX0011 | S.. | 2 | | 150-154 |
| 658 | 20 | | PA | | 3-0 | 23-22-15 | D00447A | | | | A8 | | GDX0011 | S.. | 2 | | 155-199, 275-277 |
| 658 | 20 | | PA | | 2-4 | 23-22-15 | D00447A | | | | A8 | | GDX0011 | S.. | 2 | | 278-299 |
| 658B | 24 | | PW | A8 | 4-0 | 23-22-15 | D00447A | | E05 | | | | D04737P | 55 | | | 050-099, 155-199, 275-277 |
| 658B | 24 | | PW | A8 | 8-0 | 23-22-15 | D00447A | | E05 | | | | D04737P | 40 | | | 150-154 |
| 658B | 24 | | PW | A8 | 3-2 | 23-22-15 | D00447A | | E05 | | | | D04737P | 55 | | | 278-299 |
| 658R | 24 | | PW | A8 | 0-0 | 23-22-15 | D00447A | | D05 | | | | D04737P | 54 | | | 050-099, 155-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 98

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 658R | 24 | | PW | A8 | 0-0 | 23-22-15 | D00447A | | D05 | | D04737P | | 39 | | 150-154 |
| 658Z | | | | A8 | 0-0 | 23-22-15 | D00447A | | | A8 | D04737P | | 16 | | ALL |
| 659 | 24 | | PK | | 5-0 | 23-51-11 | TB0139Z | 10 | BJ | | TB0139D | A153 | 2 | | 050-099, 150-199 |
| 659 | 24 | | PK | | 5-0 | 23-51-11 | TB0139H | 9 | 2 | | TB0139D | A153 | 2 | | 275-277 |
| 659 | 24 | | PK | | 4-2 | 23-51-11 | TB0139H | 9 | 2 | | TB0139D | A153 | 2 | | 278-299 |
| 660 | 24 | | PK | | 5-0 | 23-51-11 | D04929P | 8 | | | TB0139D | C153 | 2 | | 050-099, 150-199, 275-277 |
| 660 | 24 | | PK | | 3-10 | 23-51-11 | D04929P | 8 | | | TB0139D | C153 | 2 | | 278-299 |
| 664 | 24 | | PK | | 5-0 | 23-51-41 | TB0139Z | 10 | BJ | | TB0139D | A154 | 2 | | 050-099, 153-199 |
| 664 | 24 | | PK | | 5-0 | 23-51-41 | TB0139H | 9 | 2 | | TB0139D | A154 | 2 | | 275-277 |
| 664 | 24 | | PK | | 4-2 | 23-51-41 | TB0139H | 9 | 2 | | TB0139D | A154 | 2 | | 278-299 |
| 665 | 24 | | PK | | 6-0 | 23-51-11 | D04601P | 18 | | | TB0139Z | 9 | BJ | | 050-099 |
| 665 | 24 | | PK | | 7-0 | 23-51-11 | D04601P | 18 | | | TB0139Z | 9 | BJ | | 153-199 |
| 665 | 24 | | PK | | 7-0 | 23-51-11 | D04601P | 18 | | | TB0139H | 7 | 2 | | 275-277 |
| 665 | 24 | | PK | | 6-1 | 23-51-11 | D04601P | 18 | | | TB0139H | 7 | 2 | | 278-299 |
| 666 | 24 | | PK | | 6-0 | 23-51-21 | D04603P | 18 | | | TB0139Z | 9 | BJ | | 050-099 |
| 666 | 24 | | PK | | 7-0 | 23-51-21 | TB0139Z | 9 | BJ | | D04603P | 18 | | | 150-199 |
| 666 | 24 | | PK | | 7-0 | 23-51-21 | TB0139H | 7 | 2 | | D04603P | 18 | | | 275-277 |
| 666 | 24 | | PK | | 6-4 | 23-51-21 | TB0139H | 7 | 2 | | D04603P | 18 | | | 278-299 |
| 667 | 24 | | PK | | 6-0 | 23-51-41 | D04607P | 18 | | | TB0139Z | 9 | BJ | | 050-099 |
| 667 | 24 | | PK | | 6-0 | 23-51-41 | TB0139Z | 9 | BJ | | D04607P | 18 | | | 150-199 |
| 667 | 24 | | PK | | 6-0 | 23-51-41 | TB0139H | 7 | 2 | | D04607P | 18 | | | 275-277 |
| 667 | 24 | | PK | | 6-3 | 23-51-41 | TB0139H | 7 | 2 | | D04607P | 18 | | | 278-299 |
| 668 | 20 | | UA | | 1-6 | 23-25-13 | GDX0009 | S.. | 2 | | D00447A | | | B8 | 150, 153-199, 277-299 |
| 668B | 22 | | PR | B8 | 4-0 | 23-25-13 | D05709J | 13 | | | D00447A | H07 | | | 150, 153-155, 162-165 |
| 668B | 24 | | PW | B8 | 4-0 | 23-25-13 | D05709J | 13 | | | D00447A | H07 | | | 156-157, 166-199, 277 |
| 668B | 24 | | PW | B8 | 2-10 | 23-25-13 | D05709J | 13 | | | D00447A | H07 | | | 278-299 |
| 668R | 22 | | PR | B8 | 0-0 | 23-25-13 | D05709J | 12 | | | D00447A | G07 | | | 150, 153-155, 162-165 |
| 668R | 24 | | PW | B8 | 0-0 | 23-25-13 | D05709J | 12 | | | D00447A | G07 | | | 156-157, 166-199, 277-299 |
| 668Z | | | | B8 | 0-0 | 23-25-13 | D05709J | 8 | | | D00447A | | | B8 | 150, 153-199, 277-299 |
| 669 | 20 | | UA | | 1-6 | 23-25-13 | GDX0009 | S.. | 2 | | D00447A | | | B9 | 150, 153-199, 277-299 |
| 669B | 22 | | PR | B9 | 4-0 | 23-25-13 | D05709J | 16 | | | D00447A | D02 | | | 150, 153-155, 162-165 |
| 669B | 24 | | PW | B9 | 4-0 | 23-25-13 | D05709J | 16 | | | D00447A | D02 | | | 156-157, 166-199, 277 |
| 669B | 24 | | PW | B9 | 2-10 | 23-25-13 | D05709J | 16 | | | D00447A | D02 | | | 278-299 |
| 669R | 22 | | PR | B9 | 0-0 | 23-25-13 | D05709J | 15 | | | D00447A | C02 | | | 150, 153-155, 162-165 |
| 669R | 24 | | PW | B9 | 0-0 | 23-25-13 | D05709J | 15 | | | D00447A | C02 | | | 156-157, 166-199, 277-299 |
| 669Z | | | | B9 | 0-0 | 23-25-13 | D05709J | 14 | | | D00447A | | | B9 | 150, 153-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 99
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | | |
| 670 | 22 | | PA | 4-0 | 23-25-14 | D05709J | | 17 | | | | | TB0139G | 169 | 2 | | 150, 153-155, 162-165 |
| 670 | 24 | | PK | 4-0 | 23-25-14 | D05709J | | 17 | | | | | TB0139G | 169 | 2 | | 156-157, 166-199, 277 |
| 670 | 24 | | PK | 2-6 | 23-25-14 | D05709J | | 17 | | | | | TB0139G | 169 | 2 | | 278-299 |
| 671 | 24 | | PK | 5-0 | 23-22-12 | D04931P | | 5 | | | | | TB0139G | 170 | 2 | | 167-199 |
| 674 | 24 | | PK | 4-0 | 34-61-17 | D04813P | | 43 | | | | | TB0139D | A179 | 2 | | 157, 167-199, 277 |
| 674 | 24 | | PK | 2-4 | 34-61-17 | D04813P | | 43 | | | | | TB0139D | A179 | 2 | | 278-299 |
| 675 | 24 | | PK | 2-6 | 34-61-17 | TB0139D | | A179 | 2 | | | | TB0139D | A180 | 2 | | 157, 167-199, 277-299 |
| 676 | 24 | | PK | 2-6 | 34-61-17 | TB0139D | | A180 | 2 | | | | TB0139D | A181 | 2 | | 157, 167-199, 277-299 |
| 677 | 24 | | PK | 2-6 | 34-61-17 | TB0139D | | A181 | 2 | | | | TB0139D | A182 | 2 | | 157, 167-199, 277-299 |
| 678 | 24 | | PK | 2-6 | 34-61-17 | TB0139D | | A182 | 2 | | | | TB0139D | A183 | 2 | | 157, 167-199, 277-299 |
| 680 | 24 | | PK | 2-6 | 34-61-17 | TB0139D | | C179 | 2 | | | | TB0139Y | A177 | BJ | | 157, 167-199, 277-299 |
| 681 | 24 | | PK | 2-6 | 34-61-17 | TB0139D | | C180 | 2 | | | | TB0139Y | C177 | BJ | | 157, 167-199, 277-299 |
| 682 | 24 | | PK | 2-6 | 34-61-17 | TB0139D | | C181 | 2 | | | | TB0139Y | A178 | BJ | | 157, 167-199, 277-299 |
| 683 | 24 | | PK | 2-6 | 34-61-17 | TB0139D | | C182 | 2 | | | | TB0139Y | C178 | BJ | | 157, 167-199, 277-299 |
| 684 | 24 | | PK | 2-6 | 34-61-17 | TB0139D | | C183 | 2 | | | | TB0139Y | A184 | BJ | | 157, 167-199, 277-299 |
| 687 | 22 | | PA | 5-0 | 23-22-12 | D04953P | | 23 | | | | | D02889 | 4 | | | 275-276 |
| 687 | 22 | | PA | 4-0 | 23-22-12 | D04957P | | 54 | | | | | D02889 | 4 | | | 277 |
| 687 | 22 | | PA | 5-3 | 23-22-12 | D04957P | | 54 | | | | | D02889 | 4 | | | 278 |
| 687 | 22 | | PA | 10-0 | 23-22-12 | D04953P | | 23 | | | | | D02889 | 4 | | | 280-299 |
| 688 | 22 | | PA | 5-0 | 23-22-12 | D04953P | | 24 | | | | | D02889 | 5 | | | 275-276 |
| 688 | 22 | | PA | 4-0 | 23-22-12 | D04957P | | 55 | | | | | D02889 | 5 | | | 277 |
| 688 | 22 | | PA | 5-3 | 23-22-12 | D04957P | | 55 | | | | | D02889 | 5 | | | 278 |
| 688 | 22 | | PA | 10-0 | 23-22-12 | D04953P | | 24 | | | | | D02889 | 5 | | | 280-299 |
| 689 | 20 | | PQ | D9 | 5-0 | 23-22-12 | TB0139G | 162 | 2 | | | | D02889 | 7 | | | 275-277 |
| 689 | 20 | | PQ | D9 | 3-10 | 23-22-12 | TB0139G | 162 | 2 | | | | D02889 | 7 | | | 278 |
| 689 | 20 | | PQ | A | 5-0 | 23-22-12 | TB0139G | 162 | 2 | | | | D02889 | 7 | | | 280-299 |
| 689Z | | | | D9 | 0-0 | 23-22-12 | TB0139G | DED | | | | | D02889 | DED | | | 275-278 |
| 689Z | | | | A | 0-0 | 23-22-12 | TB0139G | DED | | | | | D02889 | DED | | | 280-299 |
| 690 | 22 | | PA | 5-0 | 23-22-12 | TB0139G | | 170 | 2 | | | | D02889 | 3 | | | 275-276, 280-299 |
| 690 | 22 | | PA | 6-0 | 23-22-12 | TB0139G | | 170 | 2 | | | | D02889 | 3 | | | 277 |
| 690 | 22 | | PA | 3-10 | 23-22-12 | TB0139G | | 170 | 2 | | | | D02889 | 3 | | | 278 |
| 691 | 20 | | PA | 5-0 | 23-22-12 | GDX0007 | | D.. | 2 | | | | D02889 | 2 | | | 275-276 |
| 691 | 20 | | PA | 4-0 | 23-22-12 | GDX0007 | | D.. | 2 | | | | D02889 | 2 | | | 277 |
| 691 | 20 | | PA | 2-8 | 23-22-12 | GDX0007 | | D.. | 2 | | | | D02889 | 2 | | | 278 |
| 691 | 20 | | PA | 3-0 | 23-22-12 | GDX0007 | | D.. | 2 | | | | D02889 | 2 | | | 280-299 |
| 692 | 24 | | PK | 4-0 | 23-22-11 | TB0139D | | C168 | 2 | | | | TB0139G | 166 | 2 | | 277 |
| 692 | 24 | | PK | 0-7 | 23-22-11 | TB0139D | | C168 | 2 | | | | TB0139G | 166 | 2 | | 278 |
| 708 | 24 | | PK | 4-0 | 23-22-12 | D00447A | | E07 | | | | | TB0139G | 170 | 2 | | 050-099, 150-199, 275-277 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 100

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 708 | 24 | | PK | 2-9 | 23-22-12 | D00447A | E07 | | | | TB0139G | 170 | 2 | | 278-299 | |
| 716 | 22 | | PA | 6-0 | 23-42-11 | D05001P | 7 | | | | TB0139F | C120 | 2 | | 050-099, 150-199, 275-277 | |
| 716 | 22 | | PA | 5-0 | 23-42-11 | D05001P | 7 | | | | TB0139F | C120 | 2 | | 278-299 | |
| 717 | 24 | | PK | 4-0 | 31-51-33 | D04813P | 24 | | | | TB0139D | A157 | 2 | | 050-099, 162-199 | |
| 717 | 24 | | PK | 6-0 | 31-51-33 | D04813P | 24 | | | | TB0139F | C141 | 2 | | 150-157, 275-277 | |
| 717 | 24 | | PK | 3-6 | 31-51-33 | D04813P | 24 | | | | TB0139F | C141 | 2 | | 278-299 | |
| 725 | 22 | | PA | 5-0 | 23-71-11 | D04633P | 2 | | | | TB0139F | A141 | 2 | | 050-099 | |
| 725 | 22 | | PA | 6-0 | 23-71-11 | D04633P | 2 | | | | TB0139F | A141 | 2 | | 150-199, 275-277 | |
| 725 | 22 | | PA | 4-1 | 23-71-11 | D04633P | 2 | | | | TB0139F | A141 | 2 | | 278-299 | |
| 726 | 22 | | PA | 7-0 | 23-71-11 | D04633P | 14 | | | | D04599P | 14 | | | 050-099, 150-199, 275-277 | |
| 726 | 22 | | PA | 6-5 | 23-71-11 | D04633P | 14 | | | | D04599P | 14 | | | 278-299 | |
| 727 | 24 | | PK | 7-0 | 23-71-11 | D04633P | 13 | | | | D04599P | 13 | | | 050-099, 150-199, 275-277 | |
| 727 | 24 | | PK | 6-5 | 23-71-11 | D04633P | 13 | | | | D04599P | 13 | | | 278-299 | |
| 728 | 24 | | PK | 7-0 | 23-71-11 | D04633P | 15 | | | | D04599P | 15 | | | 050-099, 150-199, 275-277 | |
| 728 | 24 | | PK | 6-5 | 23-71-11 | D04633P | 15 | | | | D04599P | 15 | | | 278-299 | |
| 729 | 24 | | PK | 7-0 | 23-71-11 | D04633P | 16 | | | | D04599P | 16 | | | 050-099, 150-199, 275-277 | |
| 729 | 24 | | PK | 6-5 | 23-71-11 | D04633P | 16 | | | | D04599P | 16 | | | 278-299 | |
| 730 | 24 | | PK | 7-0 | 23-71-11 | D04633P | 12 | | | | D04599P | 12 | | | 050-099, 150-199, 275-277 | |
| 730 | 24 | | PK | 6-5 | 23-71-11 | D04633P | 12 | | | | D04599P | 12 | | | 278-299 | |
| 731 | 24 | | PK | 7-0 | 23-71-11 | D04633P | 23 | | | | D04599P | 23 | | | 050-099, 150-199, 275-277 | |
| 731 | 24 | | PK | 6-5 | 23-71-11 | D04633P | 23 | | | | D04599P | 23 | | | 278-299 | |
| 732 | 24 | | PK | 7-0 | 23-71-11 | D04633P | 24 | | | | D04599P | 24 | | | 050-099, 150-199, 275-277 | |
| 732 | 24 | | PK | 6-5 | 23-71-11 | D04633P | 24 | | | | D04599P | 24 | | | 278-299 | |
| 733 | 24 | | PK | 7-0 | 23-71-11 | D04633P | 25 | | | | D04599P | 22 | | | 050-099, 150-199, 275-277 | |
| 733 | 24 | | PK | 6-5 | 23-71-11 | D04633P | 25 | | | | D04599P | 22 | | | 278-299 | |
| 734 | 24 | | PK | 7-0 | 23-71-11 | D04633P | 9 | | | | D04599P | 9 | | | 050-099, 150-199, 275-277 | |
| 734 | 24 | | PK | 6-5 | 23-71-11 | D04633P | 9 | | | | D04599P | 9 | | | 278-299 | |
| 735 | 24 | | PV | UJ | 7-0 | 23-71-11 | D04633P | 6 | | | D04599P | 6 | | | 050-099, 150-199, 275-277 | |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 101
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 735 | 24 | PV | UJ | 6-5 | 23-71-11 | D04633P | | 6 | | | D04599P | 6 | | | 278-299 | |
| 735Z | | | UJ | 0-0 | 23-71-11 | D04633P | | 5 | | | D04599P | 5 | | | ALL | |
| 736 | 24 | PV | UK | 7-0 | 23-71-11 | D04633P | | 10 | | | D04599P | 10 | | | 050-099, 150-199, 275-277 | |
| 736 | 24 | PV | UK | 6-5 | 23-71-11 | D04633P | | 10 | | | D04599P | 10 | | | 278-299 | |
| 736Z | | | UK | 0-0 | 23-71-11 | D04633P | | 11 | | | D04599P | 11 | | | ALL | |
| 737 | 24 | PK | | 5-0 | 23-71-11 | D04633P | | 8 | | | D05029P | 9 | | | 050-099 | |
| 737 | 24 | PK | | 3-6 | 23-71-11 | D04633P | | 8 | | | D05029P | 9 | | | 150-199, 275-299 | |
| 738 | 24 | PK | | 6-0 | 23-71-11 | D05029P | | 10 | | | D04599P | 8 | | | 050-099 | |
| 738 | 24 | PK | | 7-0 | 23-71-11 | D05029P | | 10 | | | D04599P | 8 | | | 150-199, 275-277 | |
| 738 | 24 | PK | | 6-1 | 23-71-11 | D05029P | | 10 | | | D04599P | 8 | | | 278-299 | |
| 743 | 24 | PK | | 6-0 | 23-51-13 | D04601P | | 38 | | | TB0139Z | 26 | BJ | | 050-099, 150-199 | |
| 743 | 24 | PK | | 6-0 | 23-51-13 | D04601P | | 38 | | | TB0139H | 26 | 2 | | 275-277 | |
| 743 | 24 | PK | | 5-3 | 23-51-13 | D04601P | | 38 | | | TB0139H | 26 | 2 | | 278-299 | |
| 745 | 24 | PK | | 6-0 | 23-51-21 | D04603P | | 38 | | | TB0139Z | 26 | BJ | | 050-099, 150-199 | |
| 745 | 24 | PK | | 6-0 | 23-51-21 | D04603P | | 38 | | | TB0139H | 26 | 2 | | 275-277 | |
| 745 | 24 | PK | | 5-5 | 23-51-21 | D04603P | | 38 | | | TB0139H | 26 | 2 | | 278-299 | |
| 746 | 24 | PK | | 6-0 | 23-51-41 | D04607P | | 38 | | | TB0139Z | 26 | BJ | | 050-099, 150-199 | |
| 746 | 24 | PK | | 6-0 | 23-51-41 | D04607P | | 38 | | | TB0139H | 26 | 2 | | 275-277 | |
| 746 | 24 | PK | | 5-5 | 23-51-41 | D04607P | | 38 | | | TB0139H | 26 | 2 | | 278-299 | |
| 751 | 24 | PK | | 6-0 | 23-12-11 | D00439B | | B14 | | | D05029P | 6 | | | 050-099 | |
| 751 | 24 | PK | | 6-0 | 23-12-11 | D05029P | | 16 | | | D00439B | B14 | | | 150-199, 275-277 | |
| 751 | 24 | PK | | 5-4 | 23-12-11 | D05029P | | 16 | | | D00439B | B14 | | | 278-299 | |
| 752 | 24 | PK | | 3-0 | 23-12-21 | D00443B | | B14 | | | TB0139G | 184 | 2 | | 050-099 | |
| 752 | 24 | PK | | 4-0 | 23-12-21 | D00443B | | B14 | | | TB0139G | 184 | 2 | | 150-156, 162-166, 275-276 | |
| 752 | 24 | PK | | 4-0 | 23-12-21 | D00443B | | B14 | | | TB0139Y | C184 | BJ | | 157, 167-199, 277 | |
| 752 | 24 | PK | | 2-8 | 23-12-21 | D00443B | | B14 | | | TB0139Y | C184 | BJ | | 278-299 | |
| 753 | 24 | PK | | 4-0 | 23-12-31 | D00445B | | B14 | | | TB0139G | 184 | 2 | | 050-099, 150-156, 162-166, 275-276 | |
| 753 | 24 | PK | | 4-0 | 23-12-31 | D00445B | | B14 | | | TB0139Y | C184 | BJ | | 157, 167-199, 277 | |
| 753 | 24 | PK | | 2-8 | 23-12-31 | D00445B | | B14 | | | TB0139Y | C184 | BJ | | 278-299 | |
| 754 | 24 | PK | | 4-0 | 23-22-12 | D00447A | | B11 | | | TB0139H | 77 | 2 | | 050-099 | |
| 754 | 24 | PK | | 4-0 | 23-22-12 | TB0139Z | | 78 | BJ | | D00447A | B11 | | | 150-199, 275-277 | |
| 754 | 24 | PK | | 3-4 | 23-22-12 | TB0139Z | | 78 | BJ | | D00447A | B11 | | | 278-299 | |
| 756 | 24 | PK | | 4-0 | 23-22-12 | D00447A | | D11 | | | TB0139H | 77 | 2 | | 050-099 | |
| 756 | 24 | PK | | 4-0 | 23-22-12 | TB0139Z | | 77 | BJ | | D00447A | D11 | | | 150-199, 275-277 | |
| 756 | 24 | PK | | 3-4 | 23-22-12 | TB0139Z | | 77 | BJ | | D00447A | D11 | | | 278-299 | |
| 772 | 24 | PK | | 4-0 | 23-11-11 | D05709J | | 11 | | | TB0139G | 181 | 2 | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 102

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 772 | 24 | | PK | | 5-0 | 23-11-11 | D05709J | | 11 | | TB0139G | 181 | 2 | | 150-156, 162-166, 275-276 |
| 772 | 24 | | PK | | 4-0 | 23-11-11 | D05709J | | 11 | | TB0139Y | C178 | BJ | | 157, 167-199, 277 |
| 772 | 24 | | PK | | 2-8 | 23-11-11 | D05709J | | 11 | | TB0139Y | C178 | BJ | | 278-299 |
| 773 | 24 | | PK | | 5-0 | 23-32-12 | D05001P | | 11 | | TB0139F | A144 | 2 | | 050-099, 150-199, 275-277 |
| 773 | 24 | | PK | | 4-1 | 23-32-12 | D05001P | | 11 | | TB0139F | A144 | 2 | | 278-299 |
| 774 | 22 | | PQ | AZ | 5-0 | 23-34-11 | TB0139F | C145 | 2 | | D05029P | 7 | | | 050-099, 150-199, 275-277 |
| 774 | 22 | | PQ | AZ | 3-9 | 23-34-11 | TB0139F | C145 | 2 | | D05029P | 7 | | | 278-299 |
| 774Z | | | | AZ | 0-0 | 23-34-11 | TB0139F | DED | | | D05029P | DED | | | ALL |
| 775 | 22 | | PQ | BZ | 4-0 | 23-34-11 | TB0139G | 108 | 2 | | D05029P | 8 | | | 050-099, 150-199, 275-277 |
| 775 | 22 | | PQ | BZ | 3-0 | 23-34-11 | TB0139G | 108 | 2 | | D05029P | 8 | | | 278-299 |
| 775Z | | | | BZ | 0-0 | 23-34-11 | TB0139G | DED | | | D05029P | DED | | | ALL |
| 778 | 24 | | PK | | 4-0 | 23-11-11 | D05709J | | 10 | | TB0139H | 64 | 2 | | 050-099 |
| 778 | 24 | | PK | | 5-0 | 23-11-11 | TB0139H | | 64 | 2 | D05709J | 10 | | | 150-199, 275-277 |
| 778 | 24 | | PK | | 2-7 | 23-11-11 | TB0139H | | 64 | 2 | D05709J | 10 | | | 278-299 |
| 779 | 24 | | PK | | 4-0 | 31-31-17 | D04813P | | 29 | | TB0139G | 181 | 2 | | 050-099 |
| 779 | 24 | | PK | | 3-0 | 31-31-17 | D04813P | | 29 | | TB0139G | 181 | 2 | | 150-156, 162-166, 275-276 |
| 779 | 24 | | PK | | 4-0 | 31-31-17 | D04813P | | 29 | | TB0139Y | C178 | BJ | | 157, 167-199, 277 |
| 779 | 24 | | PK | | 2-4 | 31-31-17 | D04813P | | 29 | | TB0139Y | C178 | BJ | | 278-299 |
| 780 | 24 | | PK | | 4-0 | 31-31-17 | D04813P | | 30 | | TB0139G | 182 | 2 | | 050-099 |
| 780 | 24 | | PK | | 3-0 | 31-31-17 | D04813P | | 30 | | TB0139G | 182 | 2 | | 150-156, 162-166, 275-276 |
| 780 | 24 | | PK | | 4-0 | 31-31-17 | D04813P | | 30 | | TB0139Y | A184 | BJ | | 157, 167-199, 277 |
| 780 | 24 | | PK | | 2-4 | 31-31-17 | D04813P | | 30 | | TB0139Y | A184 | BJ | | 278-299 |
| 781 | 24 | | PK | | 4-0 | 31-31-17 | D04813P | | 1 | | TB0139G | 179 | 2 | | 050-099 |
| 781 | 24 | | PK | | 3-0 | 31-31-17 | D04813P | | 1 | | TB0139G | 179 | 2 | | 150-156, 162-166, 275-276 |
| 781 | 24 | | PK | | 4-0 | 31-31-17 | D04813P | | 1 | | TB0139Y | C177 | BJ | | 157, 167-199, 277 |
| 781 | 24 | | PK | | 2-4 | 31-31-17 | D04813P | | 1 | | TB0139Y | C177 | BJ | | 278-299 |
| 782 | 24 | | PK | | 4-0 | 31-31-17 | D04813P | | 2 | | TB0139G | 178 | 2 | | 050-099 |
| 782 | 24 | | PK | | 3-0 | 31-31-17 | D04813P | | 2 | | TB0139G | 178 | 2 | | 150-156, 162-166, 275-276 |
| 782 | 24 | | PK | | 4-0 | 31-31-17 | D04813P | | 2 | | TB0139Y | A177 | BJ | | 157, 167-199, 277 |
| 782 | 24 | | PK | | 2-4 | 31-31-17 | D04813P | | 2 | | TB0139Y | A177 | BJ | | 278-299 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 103
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|----------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | | |
| 783 | 20 | | PA | 7-0 | 23-71-11 | D04599P | | 4 | | | | | D04633P | 1 | | | 050-099, 150-199, 275-277 |
| 783 | 20 | | PA | 6-5 | 23-71-11 | D04599P | | 4 | | | | | D04633P | 1 | | | 278-299 |
| 784 | 24 | | PK | 4-0 | 23-21-11 | D00441B | | C01 | | | | | TB0139G | 167 | 2 | | 050-099 |
| 784 | 24 | | PK | 4-0 | 23-21-11 | TB0139G | | 167 | 2 | | | | D00441B | C01 | | | 150, 152-199, 277 |
| 784 | 24 | | PK | 3-4 | 23-21-11 | TB0139G | | 167 | 2 | | | | D00441B | C01 | | | 278-299 |
| 785 | 24 | | PK | 4-0 | 23-21-11 | TB0139D | | A168 | 2 | | | | D04813P | 31 | | | 050-099 |
| 785 | 24 | | PK | 4-0 | 23-21-11 | D04813P | | 31 | | | | | TB0139D | A168 | 2 | | 150-199, 275-277 |
| 785 | 24 | | PK | 2-10 | 23-21-11 | D04813P | | 31 | | | | | TB0139D | A168 | 2 | | 278-299 |
| 786 | 24 | | PK | 6-0 | 23-34-12 | D05029P | | 14 | | | | | TB0139F | A070 | 2 | | 050-099, 150-199, 275-277 |
| 786 | 24 | | PK | 4-6 | 23-34-12 | D05029P | | 14 | | | | | TB0139F | A070 | 2 | | 278-299 |
| 787 | 24 | | PK | 6-0 | 23-34-12 | D05029P | | 15 | | | | | TB0139F | C070 | 2 | | 050-099, 150-199, 275-277 |
| 787 | 24 | | PK | 4-6 | 23-34-12 | D05029P | | 15 | | | | | TB0139F | C070 | 2 | | 278-299 |
| 788 | 24 | | PK | 6-0 | 23-34-12 | D05029P | | 5 | | | | | TB0139F | A091 | 2 | | 050-099 |
| 788 | 24 | | PK | 6-0 | 23-34-12 | D05029P | | 6 | | | | | TB0139F | A091 | 2 | | 150-199, 275-277 |
| 788 | 24 | | PK | 5-0 | 23-34-12 | D05029P | | 6 | | | | | TB0139F | A091 | 2 | | 278-299 |
| 790 | 24 | | PK | 4-0 | 23-22-11 | D00447A | | G09 | | | | | TB0139D | C168 | 2 | | 050-099, 150-199, 275-277 |
| 790 | 24 | | PK | 2-9 | 23-22-11 | D00447A | | G09 | | | | | TB0139D | C168 | 2 | | 278-299 |
| 791 | 22 | | PA | 3-0 | 23-22-11 | D00447A | | H09 | | | | | GDX0009 | S.. | 2 | | 050-099, 150, 152-199, 277 |
| 791 | 22 | | PA | 3-0 | 23-22-11 | GDX0009 | | S.. | 2 | | | | D00447A | H09 | | | 275-276 |
| 791 | 22 | | PA | 2-2 | 23-22-11 | D00447A | | H09 | | | | | GDX0009 | S.. | 2 | | 278-299 |
| 792 | 24 | | PK | 5-0 | 23-22-11 | D05001P | | 8 | | | | | TB0139D | C168 | 2 | | 050-099 |
| 792 | 24 | | PK | 4-0 | 23-22-11 | D05001P | | 8 | | | | | D00447B | F09 | | | 150, 152-166 |
| 792 | 24 | | PK | 4-0 | 23-22-11 | D05001P | | 8 | | | | | TB0139D | C168 | 2 | | 151, 275-276 |
| 792 | 24 | | PK | 5-0 | 23-22-11 | D05001P | | 8 | | | | | D00447B | F09 | | | 167-199 |
| 792 | 24 | | PK | 4-0 | 23-22-11 | D05001P | | 8 | | | | | TB0139G | 166 | 2 | | 277 |
| 792 | 24 | | PK | 3-5 | 23-22-11 | D05001P | | 8 | | | | | TB0139G | 166 | 2 | | 278 |
| 792 | 24 | | PK | 3-5 | 23-22-11 | D05001P | | 8 | | | | | TB0139D | C168 | 2 | | 280-299 |
| 793 | 24 | | PK | 4-0 | 23-22-11 | D00447B | | C09 | | | | | TB0139G | 167 | 2 | | 050-099, 150, 152-199, 277 |
| 793 | 24 | | PK | 5-0 | 23-22-11 | TB0139G | | 167 | 2 | | | | D00447B | C09 | | | 275-276 |
| 793 | 24 | | PK | 2-9 | 23-22-11 | D00447B | | C09 | | | | | TB0139G | 167 | 2 | | 278-299 |
| 794 | 24 | | PK | 6-0 | 23-51-13 | D04633P | | 26 | | | | | D04601P | 7 | | | 050-099 |
| 794 | 24 | | PK | 7-0 | 23-51-13 | D04633P | | 26 | | | | | D04601P | 7 | | | 150-199, 275-277 |
| 794 | 24 | | PK | 6-5 | 23-51-13 | D04633P | | 26 | | | | | D04601P | 7 | | | 278-299 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 104

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|-----|----|--------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | | | |
| 795 | 20 | | PA | | 5-0 | 23-51-13 | D04633P | | | | 27 | | | | GDX0007 | S.. | 2 | 050-099 |
| 795 | 20 | | PA | | 4-0 | 23-51-13 | D04633P | | | | 27 | | | | GDX0007 | S.. | 2 | 150-199, 275-277 |
| 795 | 20 | | PA | | 3-6 | 23-51-13 | D04633P | | | | 27 | | | | GDX0007 | S.. | 2 | 278-299 |
| 796 | 24 | | PK | | 7-0 | 23-51-21 | D04603P | | | | 7 | | | | D04633P | | 20 | 050-099, 150-199, 275-277 |
| 796 | 24 | | PK | | 6-7 | 23-51-21 | D04603P | | | | 7 | | | | D04633P | | 20 | 278-299 |
| 797 | 20 | | PA | | 5-0 | 23-51-21 | GDX0007 | | S.. | 2 | | | | | D04633P | | 21 | 050-099 |
| 797 | 20 | | PA | | 4-0 | 23-51-21 | GDX0007 | | S.. | 2 | | | | | D04633P | | 21 | 150-199, 275-277 |
| 797 | 20 | | PA | | 3-6 | 23-51-21 | GDX0007 | | S.. | 2 | | | | | D04633P | | 21 | 278-299 |
| 798 | 24 | | PK | | 7-0 | 23-51-41 | D04633P | | | | 18 | | | | D04607P | | 7 | 050-099 |
| 798 | 24 | | PK | | 6-0 | 23-51-41 | D04633P | | | | 18 | | | | D04607P | | 7 | 150-199, 275-277 |
| 798 | 24 | | PK | | 6-7 | 23-51-41 | D04633P | | | | 18 | | | | D04607P | | 7 | 278-299 |
| 799 | 20 | | PA | | 5-0 | 23-51-41 | D04633P | | | | 19 | | | | GDX0007 | S.. | 2 | 050-099 |
| 799 | 20 | | PA | | 4-0 | 23-51-41 | D04633P | | | | 19 | | | | GDX0007 | S.. | 2 | 150-199, 275-277 |
| 799 | 20 | | PA | | 3-6 | 23-51-41 | D04633P | | | | 19 | | | | GDX0007 | S.. | 2 | 278-299 |
| 801 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | A02 | | | | | | D01429 | | 1 | 050-099, 151, 165 |
| 801 | 24 | | PK | | 3-0 | 23-22-13 | D00447B | | A02 | | | | | | D01429 | | 1 | 275-277 |
| 801 | 24 | | PK | | 2-8 | 23-22-13 | D00447B | | A02 | | | | | | D01429 | | 1 | 278-299 |
| 802 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | B02 | | | | | | D01429 | | 2 | 150, 152-164, 166-199 |
| 803 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | C02 | | | | | | D01429 | | 3 | 150, 152-164, 166-199 |
| 804 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | D02 | | | | | | D01429 | | 4 | 150, 152-164, 166-199 |
| 805 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | E02 | | | | | | D01429 | | 5 | 050-099, 151, 165 |
| 805 | 24 | | PK | | 3-0 | 23-22-13 | D00447B | | E02 | | | | | | D01429 | | 5 | 275-277 |
| 805 | 24 | | PK | | 2-8 | 23-22-13 | D00447B | | E02 | | | | | | D01429 | | 5 | 278-299 |
| 806 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | F02 | | | | | | D01429 | | 6 | 150, 152-164, 166-199 |
| 807 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | G02 | | | | | | D01429 | | 7 | 051-099, 151-152, 155, 164-199 |
| 807 | 24 | | PK | | 3-0 | 23-22-13 | D00447B | | G02 | | | | | | D01429 | | 7 | 275-277 |
| 807 | 24 | | PK | | 2-8 | 23-22-13 | D00447B | | G02 | | | | | | D01429 | | 7 | 278-299 |
| 808 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | H02 | | | | | | D01429 | | 8 | 051-099, 151-152, 155, 164-199 |
| 808 | 24 | | PK | | 3-0 | 23-22-13 | D00447B | | H02 | | | | | | D01429 | | 8 | 275-277 |
| 808 | 24 | | PK | | 2-8 | 23-22-13 | D00447B | | H02 | | | | | | D01429 | | 8 | 278-299 |
| 809 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | J02 | | | | | | D01429 | | 9 | 050, 150, 152-162, 164, 166 |
| 809 | 24 | | PK | | 3-0 | 23-22-13 | D00447B | | J02 | | | | | | D01429 | | 9 | 275-277 |
| 809 | 24 | | PK | | 2-8 | 23-22-13 | D00447B | | J02 | | | | | | D01429 | | 9 | 278-299 |
| 810 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | K02 | | | | | | D01429 | | 10 | 050, 150, 152-162, 164, 166 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 105
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|--------|------|------|--------|------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 810 | 24 | | PK | 3-0 | 23-22-13 | D00447B | | K02 | | | D01429 | | 10 | | 275-277 | |
| 810 | 24 | | PK | 2-8 | 23-22-13 | D00447B | | K02 | | | D01429 | | 10 | | 278-299 | |
| 811 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | A03 | | | D01429 | | 11 | | 051-099, 151, 163, 165, 167-199 | |
| 812 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | B03 | | | D01429 | | 12 | | 050-099, 151, 165 | |
| 812 | 24 | | PK | 3-0 | 23-22-13 | D00447B | | B03 | | | D01429 | | 12 | | 275-277 | |
| 812 | 24 | | PK | 2-8 | 23-22-13 | D00447B | | B03 | | | D01429 | | 12 | | 278-299 | |
| 813 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | C03 | | | D01429 | | 13 | | 051-099, 151-152, 155, 164-199 | |
| 813 | 24 | | PK | 3-0 | 23-22-13 | D00447B | | C03 | | | D01429 | | 13 | | 275-277 | |
| 813 | 24 | | PK | 2-8 | 23-22-13 | D00447B | | C03 | | | D01429 | | 13 | | 278-299 | |
| 814 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | D03 | | | D01429 | | 14 | | 050, 150, 153-154, 156-162 | |
| 814 | 24 | | PK | 3-0 | 23-22-13 | D00447B | | D03 | | | D01429 | | 14 | | 275-277 | |
| 814 | 24 | | PK | 2-8 | 23-22-13 | D00447B | | D03 | | | D01429 | | 14 | | 278-299 | |
| 815 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | E03 | | | D01429 | | 15 | | 150, 153-154, 156-162, 167-199 | |
| 815 | 24 | | PK | 3-0 | 23-22-13 | D00447B | | E03 | | | D01429 | | 15 | | 275-277 | |
| 815 | 24 | | PK | 2-8 | 23-22-13 | D00447B | | E03 | | | D01429 | | 15 | | 278-299 | |
| 816 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | F03 | | | D01429 | | 16 | | 050, 150, 152-164, 166 | |
| 817 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | G03 | | | D01429 | | 17 | | 050-099, 151-152, 155, 164-166 | |
| 817 | 24 | | PK | 3-0 | 23-22-13 | D00447B | | G03 | | | D01429 | | 17 | | 275-277 | |
| 817 | 24 | | PK | 2-8 | 23-22-13 | D00447B | | G03 | | | D01429 | | 17 | | 278-299 | |
| 818 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | H03 | | | D01429 | | 18 | | 050-099, 151, 165 | |
| 818 | 24 | | PK | 3-0 | 23-22-13 | D00447B | | H03 | | | D01429 | | 18 | | 275-277 | |
| 818 | 24 | | PK | 2-8 | 23-22-13 | D00447B | | H03 | | | D01429 | | 18 | | 278-299 | |
| 819 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | J03 | | | D01429 | | 19 | | 150, 152-164, 166-199 | |
| 820 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | K03 | | | D01429 | | 20 | | 050-099, 151, 165 | |
| 820 | 24 | | PK | 3-0 | 23-22-13 | D00447B | | K03 | | | D01429 | | 20 | | 275-277 | |
| 820 | 24 | | PK | 2-8 | 23-22-13 | D00447B | | K03 | | | D01429 | | 20 | | 278-299 | |
| 821 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | A04 | | | D01429 | | 21 | | 150, 152-164, 166-199 | |
| 822 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | B04 | | | D01429 | | 22 | | 150, 152-164, 166-199 | |
| 823 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | C04 | | | D01429 | | 23 | | 050-099, 151, 165 | |
| 823 | 24 | | PK | 3-0 | 23-22-13 | D00447B | | C04 | | | D01429 | | 23 | | 275-277 | |
| 823 | 24 | | PK | 2-8 | 23-22-13 | D00447B | | C04 | | | D01429 | | 23 | | 278-299 | |
| 824 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | D04 | | | D01429 | | 24 | | 150, 152-164, 166-199 | |
| 825 | 24 | | PK | 4-0 | 23-22-13 | D00447B | | E04 | | | D01429 | | 25 | | 050-099, 151-152, 155, 163-166 | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 106

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|--------|------|------|--------|--------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 826 | 24 | | PK | 4-0 | 23-22-13 | D00447B | F04 | | | | D01429 | 26 | | | 050, 150, 152-162, 164, 166 |
| 826 | 24 | | PK | 3-0 | 23-22-13 | D00447B | F04 | | | | D01429 | 26 | | | 275-277 |
| 826 | 24 | | PK | 2-8 | 23-22-13 | D00447B | F04 | | | | D01429 | 26 | | | 278-299 |
| 827 | 24 | | PK | 4-0 | 23-22-13 | D00447B | G04 | | | | D01429 | 27 | | | 051-099, 151, 165, 167-199 |
| 828 | 24 | | PK | 4-0 | 23-22-13 | D00447B | H04 | | | | D01429 | 28 | | | 050-099, 151-152, 155, 164-166 |
| 829 | 24 | | PK | 4-0 | 23-22-13 | D00447B | J04 | | | | D01429 | 29 | | | 050, 150, 153-154, 156-162 |
| 829 | 24 | | PK | 3-0 | 23-22-13 | D00447B | J04 | | | | D01429 | 29 | | | 275-277 |
| 829 | 24 | | PK | 2-8 | 23-22-13 | D00447B | J04 | | | | D01429 | 29 | | | 278-299 |
| 830 | 24 | | PK | 4-0 | 23-22-13 | D00447B | K04 | | | | D01429 | 30 | | | 050-099, 151, 165 |
| 830 | 24 | | PK | 3-0 | 23-22-13 | D00447B | K04 | | | | D01429 | 30 | | | 275-277 |
| 830 | 24 | | PK | 2-8 | 23-22-13 | D00447B | K04 | | | | D01429 | 30 | | | 278-299 |
| 831 | 24 | | PK | 4-0 | 23-22-13 | D00447B | A05 | | | | D01429 | 31 | | | 150, 153-154, 156-162, 167-199 |
| 832 | 24 | | PK | 4-0 | 23-22-13 | D00447B | B05 | | | | D01429 | 32 | | | 150, 153-154, 156-162, 167-199 |
| 833 | 24 | | PK | 4-0 | 23-22-13 | D00447B | C05 | | | | D01429 | 33 | | | 050-099, 151-152, 155, 164-199 |
| 833 | 24 | | PK | 3-0 | 23-22-13 | D00447B | C05 | | | | D01429 | 33 | | | 275-277 |
| 833 | 24 | | PK | 2-8 | 23-22-13 | D00447B | C05 | | | | D01429 | 33 | | | 278-299 |
| 834 | 24 | | PK | 4-0 | 23-22-13 | D00447B | D05 | | | | D01429 | 34 | | | 051-099, 151, 163, 165, 167-199 |
| 834 | 24 | | PK | 3-0 | 23-22-13 | D00447B | D05 | | | | D01429 | 34 | | | 275-277 |
| 834 | 24 | | PK | 2-8 | 23-22-13 | D00447B | D05 | | | | D01429 | 34 | | | 278-299 |
| 835 | 24 | | PK | 4-0 | 23-22-13 | D00447B | E05 | | | | D01429 | 35 | | | 050-099, 151, 165 |
| 835 | 24 | | PK | 3-0 | 23-22-13 | D00447B | E05 | | | | D01429 | 35 | | | 275-277 |
| 835 | 24 | | PK | 2-8 | 23-22-13 | D00447B | E05 | | | | D01429 | 35 | | | 278-299 |
| 836 | 24 | | PK | 4-0 | 23-22-13 | D00447B | F05 | | | | D01429 | 36 | | | 050-099, 151, 165 |
| 836 | 24 | | PK | 3-0 | 23-22-13 | D00447B | F05 | | | | D01429 | 36 | | | 275-277 |
| 836 | 24 | | PK | 2-8 | 23-22-13 | D00447B | F05 | | | | D01429 | 36 | | | 278-299 |
| 837 | 24 | | PK | 4-0 | 23-22-13 | D00447B | G05 | | | | D01429 | 37 | | | 050, 151, 153-154, 156, 162, 165-199 |
| 837 | 24 | | PK | 3-0 | 23-22-13 | D00447B | G05 | | | | D01429 | 37 | | | 276 |
| 837 | 24 | | PK | 2-8 | 23-22-13 | D00447B | G05 | | | | D01429 | 37 | | | 280-299 |
| 838 | 24 | | PK | 4-0 | 23-22-13 | D00447B | H05 | | | | D01429 | 38 | | | 050, 153, 156, 164, 167-199 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 107
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|--------|------|------|--------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 838 | 24 | | PK | 3-0 | 23-22-13 | D00447B | H05 | | | | D01429 | 38 | | | 276-277 | |
| 838 | 24 | | PK | 2-8 | 23-22-13 | D00447B | H05 | | | | D01429 | 38 | | | 278-299 | |
| 839 | 24 | | PK | 4-0 | 23-22-13 | D00447B | J05 | | | | D01429 | 39 | | | 050-099, 151, 153, 155, 157-162, 164, 166 | |
| 839 | 24 | | PK | 3-0 | 23-22-13 | D00447B | J05 | | | | D01429 | 39 | | | 276-277 | |
| 840 | 24 | | PK | 4-0 | 23-22-13 | D00447B | K05 | | | | D01429 | 40 | | | 050-099, 150-152, 154-157, 163-166 | |
| 840 | 24 | | PK | 3-0 | 23-22-13 | D00447B | K05 | | | | D01429 | 40 | | | 275 | |
| 841 | 24 | | PK | 4-0 | 23-22-13 | D00447B | A06 | | | | D01429 | 41 | | | 051-099, 151, 163, 165 | |
| 841 | 24 | | PK | 3-0 | 23-22-13 | D00447B | A06 | | | | D01429 | 41 | | | 275-277 | |
| 841 | 24 | | PK | 2-8 | 23-22-13 | D00447B | A06 | | | | D01429 | 41 | | | 278-299 | |
| 842 | 24 | | PK | 4-0 | 23-22-13 | D00447B | B06 | | | | D01429 | 42 | | | 050-099, 151, 165 | |
| 842 | 24 | | PK | 3-0 | 23-22-13 | D00447B | B06 | | | | D01429 | 42 | | | 275-277 | |
| 842 | 24 | | PK | 2-8 | 23-22-13 | D00447B | B06 | | | | D01429 | 42 | | | 278-299 | |
| 843 | 24 | | PK | 4-0 | 23-22-13 | D00447B | C06 | | | | D01429 | 43 | | | 150, 152-164, 166-199 | |
| 844 | 24 | | PK | 4-0 | 23-22-13 | D00447B | D06 | | | | D01429 | 44 | | | 150, 152-164, 166-199 | |
| 844 | 24 | | PK | 3-0 | 23-22-13 | D00447B | D06 | | | | D01429 | 44 | | | 275-277 | |
| 844 | 24 | | PK | 2-8 | 23-22-13 | D00447B | D06 | | | | D01429 | 44 | | | 278-299 | |
| 845 | 24 | | PK | 4-0 | 23-22-13 | D00447B | E06 | | | | D01429 | 45 | | | 050-099, 151, 163, 165 | |
| 846 | 24 | | PK | 4-0 | 23-22-13 | D00447B | F06 | | | | D01429 | 46 | | | 050-099, 151, 163, 165 | |
| 847 | 24 | | PK | 4-0 | 23-22-13 | D00447B | G06 | | | | D01429 | 47 | | | 150, 152-162, 164, 166-199 | |
| 847 | 24 | | PK | 3-0 | 23-22-13 | D00447B | G06 | | | | D01429 | 47 | | | 275-277 | |
| 847 | 24 | | PK | 2-8 | 23-22-13 | D00447B | G06 | | | | D01429 | 47 | | | 278-299 | |
| 848 | 24 | | PK | 4-0 | 23-22-13 | D00447B | H06 | | | | D01429 | 48 | | | 050-099, 151, 165 | |
| 848 | 24 | | PK | 3-0 | 23-22-13 | D00447B | H06 | | | | D01429 | 48 | | | 275-277 | |
| 848 | 24 | | PK | 2-8 | 23-22-13 | D00447B | H06 | | | | D01429 | 48 | | | 278-299 | |
| 849 | 24 | | PK | 4-0 | 23-22-13 | D00447B | J06 | | | | D01429 | 49 | | | 150, 152-162, 164, 166-199 | |
| 849 | 24 | | PK | 3-0 | 23-22-13 | D00447B | J06 | | | | D01429 | 49 | | | 275-277 | |
| 849 | 24 | | PK | 2-8 | 23-22-13 | D00447B | J06 | | | | D01429 | 49 | | | 278-299 | |
| 850 | 24 | | PK | 4-0 | 23-22-13 | D00447B | K06 | | | | D01429 | 50 | | | 150, 152-164, 166-199 | |
| 850 | 24 | | PK | 3-0 | 23-22-13 | D00447B | K06 | | | | D01429 | 50 | | | 275-277 | |
| 850 | 24 | | PK | 2-8 | 23-22-13 | D00447B | K06 | | | | D01429 | 50 | | | 278-299 | |
| 851 | 24 | | PK | 4-0 | 23-22-13 | D00447B | A07 | | | | D01429 | 51 | | | 050-099, 151, 165 | |
| 851 | 24 | | PK | 3-0 | 23-22-13 | D00447B | A07 | | | | D01429 | 51 | | | 275-277 | |
| 851 | 24 | | PK | 2-8 | 23-22-13 | D00447B | A07 | | | | D01429 | 51 | | | 278-299 | |
| 852 | 24 | | PK | 4-0 | 23-22-13 | D00447B | B07 | | | | D01429 | 52 | | | 150, 152-162, 164, 166-199 | |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 108

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | To | | | | |
|--------------|-----------------|-------------|----|---------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|---|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 852 | 24 | | PK | | 3-0 | 23-22-13 | D00447B | | B07 | | D01429 | | 52 | | 275-277 |
| 852 | 24 | | PK | | 2-8 | 23-22-13 | D00447B | | B07 | | D01429 | | 52 | | 278-299 |
| 853 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | C07 | | D01429 | | 53 | | 050-099, 151, 163, 165 |
| 854 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | D07 | | D01429 | | 54 | | 050-099, 151, 165 |
| 854 | 24 | | PK | | 3-0 | 23-22-13 | D00447B | | D07 | | D01429 | | 54 | | 275-277 |
| 854 | 24 | | PK | | 2-8 | 23-22-13 | D00447B | | D07 | | D01429 | | 54 | | 278-299 |
| 855 | 24 | | PK | | 3-0 | 23-22-13 | D00447B | | E07 | | D01429 | | 55 | | 050-099, 275-277 |
| 855 | 24 | | PK | | 4-0 | 23-22-13 | D00447B | | E07 | | D01429 | | 55 | | 150-199 |
| 855 | 24 | | PK | | 2-8 | 23-22-13 | D00447B | | E07 | | D01429 | | 55 | | 278-299 |
| 876 | 24 | | PK | | 2-8 | 23-22-12 | TB0139Z | | 77 | BJ | TB0139Z | | 78 | BJ | 150-199, 275-299 |
| 881 | 24 | | PK | | 2-0 | 23-21-12 | D00441B | | A10 | | D01427 | | 1 | | 050-099, 150-151, 153-154, 156, 162-165 |
| 881 | 24 | | PK | | 2-3 | 23-21-12 | D00441B | | A10 | | D01427 | | 1 | | 280-299 |
| 882 | 24 | | PK | | 2-0 | 23-21-12 | D00441B | | B10 | | D01427 | | 2 | | 155, 157, 166 |
| 882 | 24 | | PK | | 3-0 | 23-21-12 | D00441B | | B10 | | D01427 | | 2 | | 277 |
| 883 | 24 | | PK | | 2-0 | 23-21-12 | D00441B | | C10 | | D01427 | | 3 | | 050-099, 150-154, 162-199 |
| 883 | 24 | | PK | | 3-0 | 23-21-12 | D00441B | | C10 | | D01427 | | 3 | | 275-277 |
| 883 | 24 | | PK | | 2-3 | 23-21-12 | D00441B | | C10 | | D01427 | | 3 | | 278-299 |
| 884 | 24 | | PK | | 2-0 | 23-21-12 | D00441B | | D10 | | D01427 | | 4 | | 050-099, 150-165, 167-199 |
| 884 | 24 | | PK | | 3-0 | 23-21-12 | D00441B | | D10 | | D01427 | | 4 | | 275-277 |
| 884 | 24 | | PK | | 2-3 | 23-21-12 | D00441B | | D10 | | D01427 | | 4 | | 278-299 |
| 885 | 24 | | PK | | 2-0 | 23-21-12 | D00441B | | A11 | | D01427 | | 5 | | 050-099, 151-154, 157-165 |
| 885 | 24 | | PK | | 3-0 | 23-21-12 | D00441B | | A11 | | D01427 | | 5 | | 275-276 |
| 886 | 24 | | PK | | 2-0 | 23-21-12 | D00441B | | B11 | | D01427 | | 6 | | 151-152, 155, 157 |
| 886 | 24 | | PK | | 2-3 | 23-21-12 | D00441B | | B11 | | D01427 | | 6 | | 278-299 |
| 887 | 24 | | PK | | 2-0 | 23-21-12 | D00441B | | C11 | | D01427 | | 7 | | 150, 155-157, 166 |
| 887 | 24 | | PK | | 2-3 | 23-21-12 | D00441B | | C11 | | D01427 | | 7 | | 280-299 |
| 888 | 24 | | PK | | 2-0 | 23-21-12 | D00441B | | D11 | | D01427 | | 8 | | 050-099, 150, 152-154, 162-165, 167-199 |
| 888 | 24 | | PK | | 2-3 | 23-21-12 | D00441B | | D11 | | D01427 | | 8 | | 278 |
| 889 | 24 | | PK | | 2-0 | 23-21-12 | D00441B | | A13 | | D01427 | | 9 | | 150, 152, 155-162 |
| 889 | 24 | | PK | | 3-0 | 23-21-12 | D00441B | | A13 | | D01427 | | 9 | | 163, 275-276 |
| 889 | 24 | | PK | | 2-3 | 23-21-12 | D00441B | | A13 | | D01427 | | 9 | | 278 |
| 890 | 24 | | PK | | 2-0 | 23-21-12 | D00441B | | B13 | | D01427 | | 10 | | 150, 155-156, 162, 165, 167-199 |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 109
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | E2-5 SHELF,L (continued) | | | | | | | | | | | | |
| 890 | 24 | | PK | 3-0 | 23-21-12 | D00441B | | B13 | | | | D01427 | | 10 | | 163 |
| 890 | 24 | | PK | 2-3 | 23-21-12 | D00441B | | B13 | | | | D01427 | | 10 | | 280-299 |
| 891 | 24 | | PK | 2-0 | 23-21-12 | D00441B | | C13 | | | | D01427 | | 11 | | 050-099, 150, 152-154, 164, 166-199 |
| 891 | 24 | | PK | 3-0 | 23-21-12 | D00441B | | C13 | | | | D01427 | | 11 | | 275-277 |
| 891 | 24 | | PK | 2-3 | 23-21-12 | D00441B | | C13 | | | | D01427 | | 11 | | 278 |
| 892 | 24 | | PK | 2-0 | 23-21-12 | D00441B | | D13 | | | | D01427 | | 12 | | 050-099, 151-166 |
| 892 | 24 | | PK | 3-0 | 23-21-12 | D00441B | | D13 | | | | D01427 | | 12 | | 275-276 |
| 892 | 24 | | PK | 2-3 | 23-21-12 | D00441B | | D13 | | | | D01427 | | 12 | | 278 |
| 893 | 24 | | PK | 2-0 | 23-21-12 | D00441B | | A15 | | | | D01427 | | 13 | | 050-099, 153, 155-156, 164, 166 |
| 893 | 24 | | PK | 3-0 | 23-21-12 | D00441B | | A15 | | | | D01427 | | 13 | | 275, 277 |
| 893 | 24 | | PK | 2-3 | 23-21-12 | D00441B | | A15 | | | | D01427 | | 13 | | 278 |
| 894 | 24 | | PK | 2-0 | 23-21-12 | D00441B | | B15 | | | | D01427 | | 14 | | 051-099, 150, 153, 155-162, 165-166 |
| 894 | 24 | | PK | 3-0 | 23-21-12 | D00441B | | B15 | | | | D01427 | | 14 | | 275-277 |
| 894 | 24 | | PK | 2-3 | 23-21-12 | D00441B | | B15 | | | | D01427 | | 14 | | 278 |
| 895 | 24 | | PK | 2-0 | 23-21-12 | D00441B | | C15 | | | | D01427 | | 15 | | 050, 150-152, 155, 157, 163-199 |
| 895 | 24 | | PK | 3-0 | 23-21-12 | D00441B | | C15 | | | | D01427 | | 15 | | 275-276 |
| 895 | 24 | | PK | 2-3 | 23-21-12 | D00441B | | C15 | | | | D01427 | | 15 | | 278 |
| 896 | 24 | | PK | 2-0 | 23-21-12 | D00441B | | D15 | | | | D01427 | | 16 | | 153-154, 162 |
| 896 | 24 | | PK | 2-3 | 23-21-12 | D00441B | | D15 | | | | D01427 | | 16 | | 278 |
| 897 | 24 | | PK | 3-0 | 23-21-12 | D00441B | | B09 | | | | D01427 | | 17 | | 050-099 |
| 897 | 24 | | PK | 2-0 | 23-21-12 | D00441B | | B09 | | | | D01427 | | 17 | | 150-199, 275-277 |
| 897 | 24 | | PK | 2-3 | 23-21-12 | D00441B | | B09 | | | | D01427 | | 17 | | 278-299 |
| 900 | 20 | | PA | 3-0 | 23-22-11 | GDY0013 | | S.. | 2 | | | D00447B | | | | FL 275-299 |
| 900B | 24 | | PW A | 0-0 | 23-22-11 | D04953P | | 19 | | | | D00447B | | K15 | | FL 275-278 |
| 900B | 24 | | PW B | 0-0 | 23-22-11 | D04953P | | 19 | | | | D00447B | | K15 | | 280-299 |
| 900R | 24 | | PW A | 10-0 | 23-22-11 | D04953P | | 18 | | | | D00447B | | J15 | | 275-278 |
| 900R | 24 | | PW B | 10-0 | 23-22-11 | D04953P | | 18 | | | | D00447B | | J15 | | 280-299 |
| 900Z | | | | 0-0 | 23-22-11 | D04953P | | 20 | | | | D00447B | | | | FL 275-278 |
| 900Z | | | | 0-0 | 23-22-11 | D04953P | | 20 | | | | D00447B | | | | FL 280-299 |
| 901 | 20 | | PQ AB | 3-0 | 23-22-11 | TB0139G | | 163 | 2 | | | D00447C | | 10 | | 150, 152-199 |
| 901Z | | | | 0-0 | 23-22-11 | TB0139G | | DED | | | | D00447C | | DED | | 150, 152-199 |
| 902 | 20 | | PQ AC | 6-0 | 23-22-12 | D04931P | | 11 | | | | TB0139G | | 163 | 2 | 150, 152-199 |
| 902Z | | | | 0-0 | 23-22-12 | D04931P | | DED | | | | TB0139G | | DED | | 150, 152-199 |
| 903 | 22 | | PA | 6-0 | 23-22-12 | D04931P | | 5 | | | | TB0139G | | 170 | 2 | 150, 152-166 |
| 904 | 22 | | PA | 10-0 | 23-22-12 | D04931P | | 12 | | | | D00447D | | J05 | | 150, 152-166 |

WIRE LIST

D280T132

91-21-11

Section W0130

Page 110

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|-----|---------------------------------|----------|---------|------|------|--------|---------|------|------|--------|--------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0139 | 286T0139 | | | | E2-5 SHELF,L (continued) | | | | | | | | | | | |
| 924B | 22 | | PR | B | 5-0 | 23-32-21 | D05109P | | 8 | | D00447B | | 12F | | 150, 152-199 | |
| 924R | 22 | | PR | B | 0-0 | 23-32-21 | D05109P | | 7 | | D00447B | | 12E | | 150, 152-199 | |
| 924Z | | | | B | 0-0 | 23-32-21 | D05109P | | | FY | D00447B | | DED | | 150, 152-199 | |
| 925B | 22 | | PR | C | 5-0 | 23-32-21 | D05109P | | 10 | | D00447B | | 12D | | 150, 152-199 | |
| 925R | 22 | | PR | C | 0-0 | 23-32-21 | D05109P | | 9 | | D00447B | | 12C | | 150, 152-199 | |
| 925Z | | | | C | 0-0 | 23-32-21 | D05109P | | | FY | D00447B | | | FZ | 150, 152-199 | |
| 926 | 22 | | PA | | 3-0 | 23-32-21 | D00447B | | | FZ | GDX0013 | | S.. | 2 | 150, 152-199 | |
| FRY | | | | | 0-0 | 23-32-21 | D05109P | | | FY | D05109P | | 11 | | 150, 152-199 | |

WIRE LIST
D280T132

91-21-11
Section W0130
Page 111 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|----------|---------|---------|-------|------|------|---------|-------|------|------|--------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0140 | 286T0140 | | | P33-THRUST REVERSER MODIF. ASSY-L2 | | | | | | | | | | | |
| 001 | 20 | PQ | AA | 2-0 | 78-34-11 | D20180 | | A2 | | | TB0458Y | C005 | BJ | | ALL |
| 001Z | | | AA | 0-0 | 78-34-11 | D20180 | | DED | | | TB0458Y | DED | | | ALL |
| 003 | 20 | PQ | AC | 1-2 | 78-34-11 | D20180 | | A1 | | | D20192 | C1 | | | ALL |
| 003Z | | | AC | 0-0 | 78-34-11 | D20180 | | | | AD | D20192 | DED | | | ALL |
| 004 | 20 | PA | | 2-1 | 78-34-11 | D20180 | | C1 | | | TB0458X | C001 | BJ | | ALL |
| 005 | 20 | PQ | AE | 2-0 | 78-34-11 | D20180 | | X1 | | | TB0458Y | C005 | BJ | | ALL |
| 005Z | | | AE | 0-0 | 78-34-11 | D20180 | | DED | | | TB0458Y | DED | | | ALL |
| 006 | 20 | PA | | 1-3 | 78-34-11 | D20180 | | X2 | | | GDX0014 | D.. | 2 | | ALL |
| 011 | 22 | PA | | 1-9 | 78-34-11 | TB0458X | | B001 | BJ | | D20188 | A1 | | | ALL |
| 012 | 20 | PA | | 1-2 | 78-34-11 | D20188 | | A3 | | | GDX0016 | D.. | 2 | | ALL |
| 013 | 22 | PQ | AM | 1-9 | 78-34-11 | TB0458X | | A001 | BJ | | D20188 | A2 | | | ALL |
| 013Z | | | AM | 0-0 | 78-34-11 | D20188 | | | | AF | TB0458X | C002 | BJ | | ALL |
| 015 | 20 | PQ | AO | 1-8 | 78-34-11 | D20188 | | X1 | | | TB0458Z | 7 | BJ | | ALL |
| 015Z | | | AO | 0-0 | 78-34-11 | D20188 | | DED | | | TB0458Z | | | AA | ALL |
| 016 | 20 | PA | | 1-2 | 78-34-11 | D20188 | | X2 | | | GDX0016 | D.. | 2 | | ALL |
| 017 | 20 | PQ | AQ | 1-11 | 78-34-11 | D20192 | | X1 | | | TB0458Z | 7 | BJ | | ALL |
| 017Z | | | AQ | 0-0 | 78-34-11 | D20192 | | DED | | | TB0458Z | | | AA | ALL |
| 018 | 20 | PQ | AR | 2-0 | 78-34-11 | D20180 | | B2 | | | TB0458Y | C005 | BJ | | ALL |
| 018Z | | | AR | 0-0 | 78-34-11 | D20180 | | DED | | | TB0458Y | DED | | | ALL |
| 023 | 20 | PA | | 1-2 | 78-34-11 | D20192 | | A3 | | | GDX0014 | D.. | 2 | | ALL |
| 025 | 20 | PA | | 1-2 | 78-34-11 | D20192 | | B3 | | | GDX0014 | D.. | 2 | | ALL |
| 026 | 20 | PQ | BA | 1-11 | 78-34-11 | D20192 | | B1 | | | TB0458Z | 7 | BJ | | ALL |
| 026Z | | | BA | 0-0 | 78-34-11 | D20192 | | DED | | | TB0458Z | | | AA | ALL |
| 027 | 20 | PA | | 1-2 | 78-34-11 | D20192 | | X2 | | | GDX0014 | D.. | 2 | | ALL |
| 028 | 20 | PQ | BC | 1-11 | 78-34-11 | D20192 | | A2 | | | TB0458Y | C006 | BJ | | ALL |
| 028Z | | | BC | 0-0 | 78-34-11 | D20192 | | DED | | | TB0458Y | | | AB | ALL |
| 029 | 20 | PA | | 1-1 | 78-34-11 | TB0458Y | | A006 | BJ | | TB0458D | C004 | 2 | | ALL |
| 030 | 20 | PQ | BE | 1-11 | 78-34-11 | D20192 | | B2 | | | TB0458Y | A006 | BJ | | ALL |
| 030Z | | | BE | 0-0 | 78-34-11 | D20192 | | DED | | | TB0458Y | | | AB | ALL |
| 031 | 20 | PA | | 1-1 | 78-34-11 | TB0458Y | | C006 | BJ | | TB0458D | C003 | 2 | | ALL |
| 032 | 20 | PA | | 1-10 | 78-34-11 | TB0458D | | A004 | 2 | | GDX0016 | D.. | 2 | | ALL |
| 033 | 20 | PA | | 1-10 | 78-34-11 | TB0458D | | A003 | 2 | | GDX0016 | D.. | 2 | | ALL |
| 034 | 20 | PA | | 1-10 | 78-34-11 | TB0458Y | | | | AB | GDX0016 | S.. | 2 | | ALL |
| 053 | 20 | PA | | 0-7 | 78-34-11 | D20192 | | D2 | | | D20192 | Y1 | | | ALL |
| 054 | 20 | PA | | 2-0 | 78-34-11 | D20192 | | Y2 | | | M01990 | A | C | | ALL |
| 055 | 20 | PA | | 1-10 | 78-34-11 | M01990 | | B | C | | GDX0016 | D.. | 2 | | ALL |
| 143 | 20 | PQ | FR | 1-5 | 78-34-11 | D20180 | | B3 | | | D20188 | B2 | | | ALL |
| 143Z | | | FR | 0-0 | 78-34-11 | D20180 | | | | AD | D20188 | DED | | | ALL |
| 153 | 20 | PA | | 1-2 | 78-34-11 | D20192 | | D3 | | | GDX0014 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0140 | 286T0140 | | | P33-THRUST REVERSER MODIF. ASSY-L2 (continued) | | | | | | | | | | | |
| 166 | 20 | PQ | GP | | 1-4 | 78-34-11 | D20188 | | B3 | | D20192 | | D1 | | ALL |
| 166Z | | | GP | | 0-0 | 78-34-11 | D20188 | | | AG | D20192 | | DED | | ALL |
| 167 | 20 | PQ | GQ | | 1-11 | 78-34-11 | D20192 | | C2 | | TB0458Z | | 7 | BJ | ALL |
| 167Z | | | GQ | | 0-0 | 78-34-11 | D20192 | | DED | | TB0458Z | | | AA | ALL |
| 168 | 20 | PQ | GR | | 1-11 | 78-34-11 | D20192 | | A1 | | TB0458Z | | 7 | BJ | ALL |
| 168Z | | | GR | | 0-0 | 78-34-11 | D20192 | | DED | | TB0458Z | | | AA | ALL |
| 173 | 20 | PA | | | 1-3 | 78-34-11 | D20180 | | | AD | GDX0014 | | S.. | 2 | ALL |
| 175 | 20 | PA | | | 1-2 | 78-34-11 | D20188 | | | AG | GDX0016 | | S.. | 2 | ALL |
| 176 | 20 | PA | | | 1-10 | 78-34-11 | GDX0016 | | S.. | 2 | TB0458Z | | | AA | ALL |
| 177 | 24 | PV | HB | | 1-7 | 78-36-11 | TB0458X | B009 | BJ | | D20110 | | 5 | | ALL |
| 177Z | | | HB | | 0-0 | 78-36-11 | TB0458X | DED | | | D20110 | | DED | | ALL |
| 178 | 24 | PV | HC | | 1-7 | 78-36-11 | TB0458X | C009 | BJ | | D20110 | | 8 | | ALL |
| 178Z | | | HC | | 0-0 | 78-36-11 | TB0458X | DED | | | D20110 | | DED | | ALL |
| 179 | 24 | PV | HD | | 1-6 | 78-36-11 | TB0458D | C014 | 2 | | D20110 | | 3 | | ALL |
| 179Z | | | HD | | 0-0 | 78-36-11 | TB0458D | DED | | | D20110 | | DED | | ALL |
| 180 | 24 | PV | HE | | 1-7 | 78-36-11 | TB0458X | A010 | BJ | | D20110 | | 1 | | ALL |
| 180Z | | | HE | | 0-0 | 78-36-11 | TB0458X | DED | | | D20110 | | DED | | ALL |
| 181 | 24 | PV | HF | | 1-6 | 78-36-11 | TB0458D | C013 | 2 | | D20110 | | 2 | | ALL |
| 181Z | | | HF | | 0-0 | 78-36-11 | TB0458D | DED | | | D20110 | | DED | | ALL |
| 182 | 24 | PV | HG | | 1-7 | 78-36-11 | TB0458X | A009 | BJ | | D20110 | | 6 | | ALL |
| 182Z | | | HG | | 0-0 | 78-36-11 | TB0458X | DED | | | D20110 | | DED | | ALL |
| 183 | 24 | PV | HH | | 1-8 | 78-36-11 | TB0458Z | 8 | BJ | | D20110 | | 7 | | ALL |
| 183Z | | | HH | | 0-0 | 78-36-11 | TB0458Z | DED | | | D20110 | | DED | | ALL |
| 184 | 20 | PA | | | 1-2 | 78-34-11 | D20188 | | | AF | GDX0016 | | S.. | 2 | ALL |
| W0141 | 286T0141 | | | E2-1 SHELF | | | | | | | | | | | |
| 001 | 22 | PA | | | 3-0 | 22-22-21 | D00667B | B05 | | | D05489J | | 7 | | ALL |
| 002 | 22 | PA | | | 3-0 | 22-22-21 | D00667A | D10 | | | D04363J | | 30 | | ALL |
| 003 | 22 | PA | | | 3-0 | 22-22-21 | D00667A | D09 | | | D04363J | | 20 | | ALL |
| 004 | 22 | PA | | | 3-0 | 22-21-21 | D04843J | 1 | | | D01261B | | G08 | | ALL |
| 005 | 22 | PA | | | 3-0 | 22-21-21 | D04843J | 3 | | | D01261B | | G07 | | ALL |
| 006 | 22 | PA | | | 4-0 | 22-21-21 | D04843J | 2 | | | TB0141G | | 91 | 2 | ALL |
| 007 | 22 | PA | | | 4-0 | 22-21-21 | D01261B | F07 | | | TB0141G | | 91 | 2 | ALL |
| 008 | 22 | PA | | | 4-0 | 22-21-21 | D05489J | 2 | | | TB0141G | | 91 | 2 | ALL |
| 009 | 22 | PA | | | 4-0 | 22-21-21 | D04363J | 31 | | | TB0141G | | 91 | 2 | ALL |
| 010 | 22 | PA | | | 3-0 | 22-21-21 | D05489J | 1 | | | D01261B | | F08 | | ALL |
| 011 | 22 | PA | | | 4-0 | 22-21-21 | D01261B | A04 | | | TB0141H | | 190 | 2 | ALL |
| 012 | 22 | PA | | | 4-0 | 22-21-21 | D04363J | 15 | | | TB0141G | | 90 | 2 | ALL |
| 013 | 22 | PA | | | 4-0 | 22-21-21 | D05489J | 3 | | | TB0141G | | 90 | 2 | ALL |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 2
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0141 | 286T0141 | | | E2-1 SHELF (continued) | | | | | | | | | | | |
| 014 | 22 | | PA | | 4-0 | 22-21-21 | D01261B | | H05 | | TB0141G | 90 | 2 | | ALL |
| 019 | 22 | | PA | | 4-0 | 22-21-21 | D01261B | | A02 | | D01257A | B15 | | | ALL |
| 020 | 22 | | PA | | 4-0 | 22-21-21 | D01261B | | C02 | | D01257A | J13 | | | ALL |
| 025 | 22 | | PA | | 4-0 | 22-21-21 | D01261B | | C01 | | D01255A | J13 | | | ALL |
| 026 | 22 | | PA | | 5-0 | 22-21-21 | D01261B | | A01 | | D01255A | B15 | | | ALL |
| 028 | 22 | | PA | | 4-0 | 22-24-21 | D05489J | | 8 | | TB0141G | 87 | 2 | | ALL |
| 029 | 22 | | PA | | 4-0 | 22-24-21 | D04363J | | 14 | | TB0141G | 87 | 2 | | ALL |
| 030 | 22 | | PA | | 4-0 | 22-24-21 | D00667A | | C14 | | TB0141G | 87 | 2 | | ALL |
| 031 | 22 | | PA | | 3-0 | 22-24-21 | D00667A | | F11 | | D05489J | 9 | | | ALL |
| 032 | 22 | | PA | | 3-0 | 22-24-21 | D00667A | | E11 | | D05489J | 10 | | | ALL |
| 035 | 22 | | PA | | 3-0 | 22-21-21 | D01261B | | H10 | | D04363J | 44 | | | ALL |
| 036 | 22 | | PA | | 1-0 | 27-61-13 | D00831B | | D06 | | D00831B | D07 | | | ALL |
| 037 | 22 | | PA | | 1-0 | 27-61-13 | D00831B | | B06 | | D00831B | B07 | | | ALL |
| 038 | 22 | | PA | | 1-0 | 27-61-17 | D00833B | | D11 | | D00833B | D12 | | | ALL |
| 042 | 22 | | PA | | 1-0 | 27-61-17 | D00833B | | D13 | | D00833B | D14 | | | ALL |
| 043 | 22 | | PA | | 1-0 | 27-61-17 | D00833B | | B13 | | D00833B | B14 | | | ALL |
| 049 | 22 | | PA | | 3-0 | 27-09-11 | D01257B | | E15 | | D04257J | 2 | | | ALL |
| 050 | 22 | | PA | | 3-0 | 27-09-11 | D04257J | | 3 | | TB0141H | 190 | 2 | | ALL |
| 051 | 22 | | PA | | 3-0 | 27-09-11 | D01257B | | A15 | | TB0141H | 190 | 2 | | ALL |
| 052 | 22 | | PA | | 6-0 | 27-09-11 | D01255B | | A15 | | TB0141H | 190 | 2 | | ALL |
| 065 | 22 | | PA | | 4-0 | 27-09-13 | D00833A | | A12 | | GDX0011 | D.. | 2 | | ALL |
| 066 | 22 | | PA | | 4-0 | 27-09-12 | D04363J | | 3 | | TB0141H | 186 | 2 | | ALL |
| 067 | 22 | | PA | | 4-0 | 27-09-12 | D05489J | | 11 | | TB0141H | 186 | 2 | | ALL |
| 068 | 22 | | PA | | 5-0 | 27-09-12 | D01265B | | D07 | | TB0141H | 186 | 2 | | ALL |
| 069 | 22 | | PA | | 4-0 | 27-09-12 | D01261B | | H04 | | TB0141H | 186 | 2 | | ALL |
| 070 | 22 | | PA | | 4-0 | 27-09-12 | D00667A | | E14 | | TB0141H | 186 | 2 | | ALL |
| 071 | 22 | | PA | | 4-0 | 27-09-12 | D00835A | | D01 | | TB0141H | 186 | 2 | | ALL |
| 072 | 22 | | PA | | 5-0 | 27-09-12 | D00833B | | D10 | | TB0141H | 186 | 2 | | ALL |
| 073 | 22 | | PA | | 5-0 | 27-09-12 | D00831B | | D02 | | TB0141H | 186 | 2 | | ALL |
| 074 | 22 | | PA | | 4-0 | 27-09-13 | D05489J | | 12 | | TB0141H | 182 | 2 | | ALL |
| 075 | 22 | | PA | | 4-0 | 27-09-13 | D00835A | | A13 | | TB0141H | 182 | 2 | | ALL |
| 076 | 22 | | PA | | 5-0 | 27-09-13 | D01265B | | B03 | | TB0141H | 182 | 2 | | ALL |
| 077 | 22 | | PA | | 4-0 | 27-09-13 | D01261B | | B12 | | TB0141H | 182 | 2 | | ALL |
| 078 | 22 | | PA | | 4-0 | 27-09-13 | D00667B | | F05 | | TB0141H | 182 | 2 | | ALL |
| 079 | 22 | | PA | | 5-0 | 27-09-13 | D00831A | | A13 | | TB0141H | 182 | 2 | | ALL |
| 080 | 22 | | PA | | 4-0 | 27-09-13 | D04363J | | 28 | | TB0141H | 182 | 2 | | ALL |
| 081 | 22 | | PA | | 4-0 | 27-09-13 | D05489J | | 13 | | TB0141H | 184 | 2 | | ALL |
| 082 | 22 | | PA | | 4-0 | 27-09-13 | D00835A | | A12 | | TB0141H | 184 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|---|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0141 | 286T0141 | | | E2-1 SHELF (continued) | | | | | | | | | | | |
| 083 | 22 | | PA | | 2-0 | 27-09-13 | D01265B | A03 | | | GDX0005 | D.. | 2 | | 050-099, 150-199, 275-278 280-299 |
| 083 | 22 | | PA | | 5-0 | 27-09-13 | D01265B | A03 | | | TB0141H | 184 | 2 | | |
| 084 | 22 | | PA | | 4-0 | 27-09-13 | D01261B | A12 | | | TB0141H | 184 | 2 | | ALL |
| 085 | 22 | | PA | | 4-0 | 27-09-13 | D00667B | F06 | | | TB0141H | 184 | 2 | | ALL |
| 086 | 22 | | PA | | 5-0 | 27-09-13 | D00831A | A12 | | | TB0141H | 184 | 2 | | ALL |
| 087 | 22 | | PA | | 4-0 | 27-09-13 | D04363J | 29 | | | TB0141H | 184 | 2 | | ALL |
| 089 | 22 | | PA | | 4-0 | 27-09-14 | D05489J | 49 | | | TB0141G | 84 | 2 | | ALL |
| 090 | 22 | | PA | | 5-0 | 27-09-14 | D01255B | A13 | | | TB0141G | 84 | 2 | | ALL |
| 091 | 22 | | PA | | 5-0 | 27-09-14 | D01265A | C15 | | | D05489J | 4 | | | ALL |
| 094 | 22 | | PA | | 4-0 | 27-09-14 | D00835A | C13 | | | TB0141H | 85 | 2 | | ALL |
| 095 | 22 | | PA | | 4-0 | 27-09-14 | TB0141H | 85 | 2 | | D05489J | 22 | | | ALL |
| 096 | 22 | | PA | | 5-0 | 27-09-14 | D00833A | C13 | | | TB0141H | 85 | 2 | | ALL |
| 097 | 22 | | PA | | 5-0 | 27-09-14 | D00831A | C13 | | | TB0141H | 85 | 2 | | ALL |
| 098 | 22 | | PA | | 3-0 | 27-09-14 | D01257B | A13 | | | TB0141G | 84 | 2 | | ALL |
| 099 | 22 | | PA | | 3-0 | 27-11-22 | D00667A | E07 | | | D05489J | 17 | | | ALL |
| 100 | 22 | | PA | | 3-0 | 27-11-22 | D00667A | E08 | | | D05489J | 18 | | | ALL |
| 101 | 22 | | PQ | EA | 4-0 | 27-41-21 | D00667A | F09 | | | D05139J | 13 | | | ALL |
| 101Z | | | | EA | 0-0 | 27-41-21 | D00667A | DED | | | D05139J | DED | | | ALL |
| 102 | 22 | | PQ | EB | 4-0 | 27-41-21 | D00667A | F10 | | | D05139J | 14 | | | ALL |
| 102Z | | | | EB | 0-0 | 27-41-21 | D00667A | DED | | | D05139J | DED | | | ALL |
| 103 | 22 | | PA | | 4-0 | 27-41-21 | D00667A | F07 | | | TB0141G | 83 | 2 | | ALL |
| 104 | 22 | | PA | | 4-0 | 27-41-21 | D00667A | F08 | | | TB0141G | 83 | 2 | | ALL |
| 105 | 22 | | PA | | 3-0 | 27-41-21 | D04257J | 1 | | | TB0141G | 83 | 2 | | ALL |
| 106 | 22 | | PA | | 3-0 | 27-41-21 | D00667A | A13 | | | D05489J | 15 | | | ALL |
| 107 | 22 | | PA | | 3-0 | 27-41-21 | D00667A | A14 | | | D05489J | 16 | | | ALL |
| 108 | 22 | | PA | | 3-0 | 27-41-21 | D00667A | F12 | | | D05489J | 19 | | | ALL |
| 109 | 22 | | PA | | 5-0 | 27-41-21 | D00667A | G13 | | | D01255A | H12 | | | ALL |
| 110 | 22 | | PA | | 5-0 | 27-41-21 | D00667A | G14 | | | D01255A | A14 | | | ALL |
| 112 | 22 | | PA | | 4-0 | 27-41-21 | D00667A | J13 | | | D01257A | H12 | | | ALL |
| 113 | 22 | | PA | | 4-0 | 27-41-21 | D00667A | J14 | | | D01257A | A14 | | | ALL |
| 115 | 22 | | PA | | 4-0 | 27-61-11 | D05489J | 20 | | | TB0141H | 81 | 2 | | ALL |
| 116 | 22 | | PA | | 4-0 | 27-61-11 | D04363J | 26 | | | TB0141H | 81 | 2 | | ALL |
| 117 | 22 | | PA | | 4-0 | 27-61-11 | D00835A | E01 | | | TB0141H | 81 | 2 | | ALL |
| 118 | 22 | | PA | | 5-0 | 27-61-11 | D00833B | E10 | | | TB0141H | 81 | 2 | | ALL |
| 119 | 22 | | PA | | 5-0 | 27-61-11 | D00831B | E02 | | | TB0141H | 81 | 2 | | ALL |
| 120 | 22 | | PA | | 3-0 | 27-61-12 | D05489J | 21 | | | TB0141H | 79 | 2 | | ALL |
| 121 | 22 | | PA | | 3-0 | 27-61-12 | D04843J | 4 | | | TB0141H | 79 | 2 | | ALL |
| 122 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | B13 | | | TB0141H | 79 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0140
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0141 | 286T0141 | | | E2-1 SHELF (continued) | | | | | | | | | | | | |
| 123 | 22 | | PA | 5-0 | 27-61-12 | D00833A | | B13 | | | | TB0141H | 79 | 2 | | ALL |
| 124 | 22 | | PA | 5-0 | 27-61-12 | D00831A | | B13 | | | | TB0141H | 79 | 2 | | ALL |
| 127 | 22 | | PA | 5-0 | 27-61-13 | D01255B | | G01 | | | | D01257B | E01 | | | ALL |
| 128 | 22 | | PA | 4-0 | 27-61-13 | D01257B | | C01 | | | | TB0141H | 180 | 2 | | ALL |
| 129 | 22 | | PA | 5-0 | 27-61-13 | D00831A | | A15 | | | | TB0141H | 190 | 2 | | ALL |
| 132 | 22 | | PA | 3-0 | 27-61-13 | D01255A | | C14 | | | | D00831B | G06 | | | ALL |
| 133 | 22 | | PA | 3-0 | 27-61-13 | D01255A | | K12 | | | | D00831B | G04 | | | ALL |
| 135 | 22 | | PA | 5-0 | 27-61-13 | D00831B | | F06 | | | | D01257A | C14 | | | ALL |
| 136 | 22 | | PA | 5-0 | 27-61-13 | D00831B | | F04 | | | | D01257A | K12 | | | ALL |
| 139 | 22 | | PA | 5-0 | 27-61-17 | D00833A | | A15 | | | | TB0141H | 190 | 2 | | ALL |
| 141 | 22 | | PA | 4-0 | 27-61-17 | D00833B | | G14 | | | | D01255A | C15 | | | ALL |
| 142 | 22 | | PA | 4-0 | 27-61-17 | D00833B | | G12 | | | | D01255A | K13 | | | ALL |
| 144 | 22 | | PA | 4-0 | 27-61-17 | D00833B | | F14 | | | | D01257A | C15 | | | ALL |
| 145 | 22 | | PA | 4-0 | 27-61-17 | D00833B | | F12 | | | | D01257A | K13 | | | ALL |
| 153 | 22 | | PA | 1-0 | 27-61-18 | D00835A | | D02 | | | | D00835A | D03 | | | ALL |
| 157 | 22 | | PA | 1-0 | 27-61-18 | D00835A | | D04 | | | | D00835A | D05 | | | ALL |
| 158 | 22 | | PA | 1-0 | 27-61-18 | D00835A | | B04 | | | | D00835A | B05 | | | ALL |
| 159 | 22 | | PA | 3-0 | 27-61-18 | D04363J | | 1 | | | | TB0141G | 177 | 2 | | ALL |
| 160 | 22 | | PA | 3-0 | 27-61-18 | D04363J | | 2 | | | | TB0141G | 176 | 2 | | ALL |
| 163 | 22 | | PA | 5-0 | 27-61-18 | D01255A | | F13 | | | | D00835A | E11 | | | ALL |
| 164 | 22 | | PA | 5-0 | 27-61-18 | D01255A | | J12 | | | | D00835A | G03 | | | ALL |
| 165 | 22 | | PA | 5-0 | 27-61-18 | D01255A | | B14 | | | | D00835A | G05 | | | ALL |
| 167 | 22 | | PA | 4-0 | 27-61-18 | D00835A | | A15 | | | | TB0141H | 190 | 2 | | ALL |
| 171 | 22 | | PA | 3-0 | 27-61-18 | D00835A | | E12 | | | | D01257A | F13 | | | ALL |
| 172 | 22 | | PA | 3-0 | 27-61-18 | D00835A | | F03 | | | | D01257A | J12 | | | ALL |
| 173 | 22 | | PA | 3-0 | 27-61-18 | D00835A | | F05 | | | | D01257A | B14 | | | ALL |
| 175 | 22 | | PA | 4-0 | 27-21-22 | D01265B | | A12 | | | | D01255A | A15 | | | ALL |
| 176 | 22 | | PA | 4-0 | 27-21-22 | D01265B | | D12 | | | | D01255A | H13 | | | ALL |
| 177 | 22 | | PA | 5-0 | 27-21-22 | D01257A | | A15 | | | | D01265B | A13 | | | ALL |
| 178 | 22 | | PA | 5-0 | 27-21-22 | D01257A | | H13 | | | | D01265B | D13 | | | ALL |
| 181 | 22 | | PA | 3-0 | 27-41-21 | D00667A | | E12 | | | | D05489J | 23 | | | ALL |
| 182 | 22 | | PA | 4-0 | 27-21-12 | D01265B | | D04 | | | | D05489J | 30 | | | ALL |
| 183 | 22 | | PA | 4-0 | 27-21-12 | D01265B | | C08 | | | | D05489J | 31 | | | ALL |
| 184 | 22 | | PA | 4-0 | 27-21-12 | D01265B | | B01 | | | | D05489J | 37 | | | ALL |
| 185 | 22 | | PA | 4-0 | 27-21-12 | D01265B | | A01 | | | | D05489J | 38 | | | ALL |
| 186 | 22 | | PA | 4-0 | 27-21-12 | D01265B | | D01 | | | | D05489J | 39 | | | ALL |
| 187 | 22 | | PA | 4-0 | 27-21-22 | D00667A | | K15 | | | | D01265B | D08 | | | ALL |
| 189 | 22 | | PA | 3-0 | 27-41-21 | D04363J | | 40 | | | | D00667A | B13 | | | ALL |
| 190 | 22 | | PA | 3-0 | 27-41-21 | D04363J | | 39 | | | | D00667A | B14 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0141 | 286T0141 | | | E2-1 SHELF (continued) | | | | | | | | | | | |
| 191 | 22 | | PA | | 3-0 | 27-41-21 | D04363J | | | | D05489J | 42 | | | ALL |
| 192 | 22 | | PA | | 3-0 | 27-41-21 | D04363J | | | | D05489J | 43 | | | ALL |
| 193 | 22 | | PA | | 3-0 | 27-61-17 | D04363J | | | | D00833B | H12 | | | ALL |
| 194 | 20 | | PA | | 3-0 | 27-61-17 | D04363J | | | | GDX0008 | D.. | 2 | | ALL |
| 195 | 22 | | PA | | 3-0 | 27-61-17 | D00833B | | C10 | | D00667A | A15 | | | ALL |
| 201 | 20 | | UA | | 0-18 | 22-22-21 | GDX0009 | | S.. | 2 | D04363J | | | FJ | ALL |
| 201B | 24 | | PW | IA | 3-0 | 22-22-21 | D04363J | | | | D00667A | D08 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 22-22-21 | D04363J | | | | D00667A | D07 | | | ALL |
| 201Z | | | | IA | 0-0 | 22-22-21 | D04363J | | | | D00667A | DED | | | ALL |
| 202 | 20 | | UA | | 0-18 | 22-21-21 | D04363J | | | | GDX0009 | S.. | 2 | | ALL |
| 202B | 24 | | PW | IB | 3-0 | 22-21-21 | D04363J | | 11 | | D01261B | K05 | | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 22-21-21 | D04363J | | 10 | | D01261B | K04 | | | ALL |
| 202Z | | | | IB | 0-0 | 22-21-21 | D04363J | | | | D01261B | DED | | | ALL |
| 205B | 24 | | PW | IE | 4-0 | 22-21-21 | D01261A | | K15 | | TB0141G | 189 | 2 | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 22-21-21 | D01261A | | K14 | | TB0141G | 188 | 2 | | ALL |
| 205Z | | | | IE | 0-0 | 22-21-21 | TB0141G | | | | D01261A | DED | | | ALL |
| 206 | 20 | | UA | | 0-18 | 27-11-22 | D04363J | | | | GDX0009 | S.. | 2 | | ALL |
| 206B | 24 | | PW | IF | 4-0 | 27-11-22 | D04363J | | 24 | | TB0141G | 189 | 2 | | ALL |
| 206R | 24 | | PW | IF | 0-0 | 27-11-22 | D04363J | | 23 | | TB0141G | 188 | 2 | | ALL |
| 206Z | | | | IF | 0-0 | 27-11-22 | D04363J | | | | TB0141G | | | FC | ALL |
| 207B | 24 | | PW | IG | 4-0 | 27-11-22 | D00667A | | D12 | | TB0141G | 189 | 2 | | ALL |
| 207R | 24 | | PW | IG | 0-0 | 27-11-22 | D00667A | | D11 | | TB0141G | 188 | 2 | | ALL |
| 207Z | | | | IG | 0-0 | 27-11-22 | D00667A | | DED | | TB0141G | | | FC | ALL |
| 209B | 22 | | PB | II | 3-0 | 27-41-21 | D04363J | | 22 | | D00667A | E10 | | | ALL |
| 209R | 22 | | PB | II | 0-0 | 27-41-21 | D04363J | | 21 | | D00667A | E09 | | | ALL |
| 210B | 22 | | PB | IJ | 4-0 | 27-61-13 | D05139J | | 9 | | TB0141H | 180 | 2 | | ALL |
| 210R | 22 | | PB | IJ | 0-0 | 27-61-13 | D05139J | | 8 | | TB0141H | 178 | 2 | | ALL |
| 211B | 22 | | PB | IK | 4-0 | 27-61-13 | D05139J | | 2 | | TB0141H | 180 | 2 | | ALL |
| 211R | 22 | | PB | IK | 0-0 | 27-61-13 | D05139J | | 1 | | TB0141H | 178 | 2 | | ALL |
| 212B | 22 | | PB | IL | 5-0 | 27-61-13 | D01255B | | C01 | | TB0141H | 180 | 2 | | ALL |
| 212R | 22 | | PB | IL | 0-0 | 27-61-13 | D01255B | | A01 | | TB0141H | 178 | 2 | | ALL |
| 213B | 22 | | PB | IM | 5-0 | 27-61-13 | D00831B | | J07 | | TB0141H | 180 | 2 | | ALL |
| 213R | 22 | | PB | IM | 0-0 | 27-61-13 | D00831B | | K07 | | TB0141H | 178 | 2 | | ALL |
| 214B | 22 | | PB | IN | 4-0 | 27-61-17 | D00833B | | J15 | | TB0141H | 180 | 2 | | ALL |
| 214R | 22 | | PB | IN | 0-0 | 27-61-17 | D00833B | | K15 | | TB0141H | 178 | 2 | | ALL |
| 215B | 22 | | PB | IO | 4-0 | 27-61-18 | D05487J | | 9 | | TB0141G | 175 | 2 | | ALL |
| 215R | 22 | | PB | IO | 0-0 | 27-61-18 | D05487J | | 8 | | TB0141G | 174 | 2 | | ALL |
| 216B | 22 | | PB | IP | 3-0 | 27-61-18 | D00835A | | J11 | | TB0141G | 175 | 2 | | ALL |
| 216R | 22 | | PB | IP | 0-0 | 27-61-18 | D00835A | | K11 | | TB0141G | 174 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0140
 Page 6
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0141 | 286T0141 | | | E2-1 SHELF (continued) | | | | | | | | | | | | |
| 217B | 22 | PB | IQ | 4-0 | 27-61-18 | D05487J | | 15 | | | | TB0141G | 175 | 2 | | ALL |
| 217R | 22 | PB | IQ | 0-0 | 27-61-18 | D05487J | | 14 | | | | TB0141G | 174 | 2 | | ALL |
| 218B | 22 | PB | IR | 3-0 | 27-61-18 | D00835A | | G08 | | | | TB0141G | 176 | 2 | | ALL |
| 218R | 22 | PB | IR | 0-0 | 27-61-18 | D00835A | | G09 | | | | TB0141F | A173 | 2 | | ALL |
| 219B | 22 | PB | IS | 3-0 | 27-61-18 | D00835A | | G11 | | | | TB0141G | 177 | 2 | | ALL |
| 219R | 22 | PB | IS | 0-0 | 27-61-18 | D00835A | | G10 | | | | TB0141F | C173 | 2 | | ALL |
| 220B | 22 | PB | IT | 3-0 | 27-61-18 | D00835A | | J06 | | | | TB0141H | 180 | 2 | | ALL |
| 220R | 22 | PB | IT | 0-0 | 27-61-18 | D00835A | | K06 | | | | TB0141H | 178 | 2 | | ALL |
| 221B | 22 | PB | IU | 4-0 | 27-21-12 | D01265A | | A04 | | | | D05489J | 36 | | | ALL |
| 221R | 22 | PB | IU | 0-0 | 27-21-12 | D01265A | | A05 | | | | D05489J | 35 | | | ALL |
| 223B | 22 | PB | IW | 4-0 | 27-61-18 | D05487J | | 3 | | | | TB0141G | 176 | 2 | | ALL |
| 223R | 22 | PB | IW | 0-0 | 27-61-18 | D05487J | | 1 | | | | TB0141F | A173 | 2 | | ALL |
| 224B | 22 | PB | IX | 4-0 | 27-61-18 | D05487J | | 11 | | | | TB0141G | 177 | 2 | | ALL |
| 224R | 22 | PB | IX | 0-0 | 27-61-18 | D05487J | | 10 | | | | TB0141F | C173 | 2 | | ALL |
| 225B | 22 | PB | IY | 4-0 | 27-21-22 | D00667A | | K14 | | | | D01265B | D10 | | | ALL |
| 225R | 22 | PB | IY | 0-0 | 27-21-22 | D00667A | | K13 | | | | D01265B | D09 | | | ALL |
| 284B | 24 | PW | LI | 6-0 | 22-21-31 | D05489J | | 28 | | | | TB0141Z | 55 | BJ | | 150-199, 275-299 |
| 284R | 24 | PW | LI | 0-0 | 22-21-31 | D05489J | | 27 | | | | TB0141Z | 54 | BJ | | 150-199, 275-299 |
| 284Z | | | LI | 0-0 | 22-21-31 | D05489J | | 26 | | | | TB0141Z | | | LI | 150-199, 275-299 |
| 285 | 20 | UA | | 1-6 | 22-21-31 | D01261B | | | | LJ | | GDX0008 | S.. | 2 | | 150-199, 275-299 |
| 285B | 24 | PW | LJ | 6-0 | 22-21-31 | D01261B | | H15 | | | | TB0141Z | 55 | BJ | | 150-199, 275-299 |
| 285R | 24 | PW | LJ | 0-0 | 22-21-31 | D01261B | | H14 | | | | TB0141Z | 54 | BJ | | 150-199, 275-299 |
| 285Z | | | LJ | 0-0 | 22-21-31 | D01261B | | | | LJ | | TB0141Z | | | LI | 150-199, 275-299 |
| 286B | 24 | PW | LK | 6-0 | 22-21-31 | D05489J | | 34 | | | | TB0141Z | 55 | BJ | | 150-199, 275-299 |
| 286R | 24 | PW | LK | 0-0 | 22-21-31 | D05489J | | 33 | | | | TB0141Z | 54 | BJ | | 150-199, 275-299 |
| 286Z | | | LK | 0-0 | 22-21-31 | D05489J | | 32 | | | | TB0141Z | | | LI | 150-199, 275-299 |
| 301B | 22 | PC | MA | 4-0 | 27-61-13 | D05139J | | 4 | | | | TB0141G | 77 | 2 | | ALL |
| 301R | 22 | PC | MA | 0-0 | 27-61-13 | D05139J | | 6 | | | | TB0141G | 76 | 2 | | ALL |
| 301Y | 22 | PC | MA | 0-0 | 27-61-13 | D05139J | | 7 | | | | TB0141G | 78 | 2 | | ALL |
| 302B | 22 | PC | MB | 5-0 | 27-61-13 | D00831B | | J06 | | | | TB0141G | 77 | 2 | | ALL |
| 302R | 22 | PC | MB | 0-0 | 27-61-13 | D00831B | | J04 | | | | TB0141G | 76 | 2 | | ALL |
| 302Y | 22 | PC | MB | 0-0 | 27-61-13 | D00831B | | J05 | | | | TB0141G | 78 | 2 | | ALL |
| 303B | 22 | PC | MC | 4-0 | 27-61-13 | D05139J | | 12 | | | | TB0141G | 74 | 2 | | ALL |
| 303R | 22 | PC | MC | 0-0 | 27-61-13 | D05139J | | 3 | | | | TB0141G | 73 | 2 | | ALL |
| 303Y | 22 | PC | MC | 0-0 | 27-61-13 | D05139J | | 5 | | | | TB0141G | 75 | 2 | | ALL |
| 304B | 22 | PC | MD | 4-0 | 27-61-13 | D00831B | | K06 | | | | TB0141G | 74 | 2 | | ALL |
| 304R | 22 | PC | MD | 0-0 | 27-61-13 | D00831B | | K04 | | | | TB0141G | 73 | 2 | | ALL |
| 304Y | 22 | PC | MD | 0-0 | 27-61-13 | D00831B | | K05 | | | | TB0141G | 75 | 2 | | ALL |
| 305B | 22 | PC | ME | 4-0 | 27-61-17 | D00833B | | K14 | | | | TB0141G | 74 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0141 | 286T0141 | | | E2-1 SHELF (continued) | | | | | | | | | | | |
| 305R | 22 | PC | ME | | 0-0 | 27-61-17 | D00833B | | | | K12 | TB0141G | 73 | 2 | ALL |
| 305Y | 22 | PC | ME | | 0-0 | 27-61-17 | D00833B | | | | K13 | TB0141G | 75 | 2 | ALL |
| 306B | 22 | PC | MF | | 4-0 | 27-61-17 | D00833B | | | | J14 | TB0141G | 77 | 2 | ALL |
| 306R | 22 | PC | MF | | 0-0 | 27-61-17 | D00833B | | | | J12 | TB0141G | 76 | 2 | ALL |
| 306Y | 22 | PC | MF | | 0-0 | 27-61-17 | D00833B | | | | J13 | TB0141G | 78 | 2 | ALL |
| 307B | 22 | PC | MG | | 4-0 | 27-61-18 | D00835A | | | | K05 | TB0141G | 74 | 2 | ALL |
| 307R | 22 | PC | MG | | 0-0 | 27-61-18 | D00835A | | | | K03 | TB0141G | 73 | 2 | ALL |
| 307Y | 22 | PC | MG | | 0-0 | 27-61-18 | D00835A | | | | K04 | TB0141G | 75 | 2 | ALL |
| 308B | 22 | PC | MH | | 4-0 | 27-61-18 | D00835A | | | | J05 | TB0141G | 77 | 2 | ALL |
| 308R | 22 | PC | MH | | 0-0 | 27-61-18 | D00835A | | | | J03 | TB0141G | 76 | 2 | ALL |
| 308Y | 22 | PC | MH | | 0-0 | 27-61-18 | D00835A | | | | J04 | TB0141G | 78 | 2 | ALL |
| 309B | 22 | PC | MI | | 4-0 | 27-61-18 | D00835A | | | | J10 | D05487J | 6 | | ALL |
| 309R | 22 | PC | MI | | 0-0 | 27-61-18 | D00835A | | | | J08 | D05487J | 12 | | ALL |
| 309Y | 22 | PC | MI | | 0-0 | 27-61-18 | D00835A | | | | J09 | D05487J | 13 | | ALL |
| 310B | 22 | PC | MJ | | 4-0 | 27-61-18 | D00835A | | | | K10 | D05487J | 4 | | ALL |
| 310R | 22 | PC | MJ | | 0-0 | 27-61-18 | D00835A | | | | K08 | D05487J | 5 | | ALL |
| 310Y | 22 | PC | MJ | | 0-0 | 27-61-18 | D00835A | | | | K09 | D05487J | 7 | | ALL |
| 312B | 22 | PC | ML | | 5-0 | 22-21-21 | D01261B | | | | K02 | D01255A | K09 | | ALL |
| 312R | 22 | PC | ML | | 0-0 | 22-21-21 | D01261B | | | | K01 | D01255A | K08 | | ALL |
| 312Y | 22 | PC | ML | | 0-0 | 22-21-21 | D01261B | | | | J01 | D01255A | J08 | | ALL |
| 313B | 22 | PC | MM | | 5-0 | 22-21-21 | D01261B | | | | H01 | D01255A | J09 | | ALL |
| 313R | 22 | PC | MM | | 0-0 | 22-21-21 | D01261B | | | | J02 | D01255A | K10 | | ALL |
| 313Y | 22 | PC | MM | | 0-0 | 22-21-21 | D01261B | | | | H02 | D01255A | J10 | | ALL |
| 314B | 22 | PC | MN | | 3-0 | 22-21-21 | D01261B | | | | G02 | D01257A | K09 | | ALL |
| 314R | 22 | PC | MN | | 0-0 | 22-21-21 | D01261B | | | | G01 | D01257A | K08 | | ALL |
| 314Y | 22 | PC | MN | | 0-0 | 22-21-21 | D01261B | | | | F01 | D01257A | J08 | | ALL |
| 315B | 22 | PC | MO | | 3-0 | 22-21-21 | D01261B | | | | E01 | D01257A | J09 | | ALL |
| 315R | 22 | PC | MO | | 0-0 | 22-21-21 | D01261B | | | | F02 | D01257A | K10 | | ALL |
| 315Y | 22 | PC | MO | | 0-0 | 22-21-21 | D01261B | | | | E02 | D01257A | J10 | | ALL |
| 316B | 22 | PC | MP | | 4-0 | 27-41-21 | D00667B | | | | K03 | D01255A | H09 | | ALL |
| 316R | 22 | PC | MP | | 0-0 | 27-41-21 | D00667B | | | | K02 | D01255A | H08 | | ALL |
| 316Y | 22 | PC | MP | | 0-0 | 27-41-21 | D00667B | | | | K04 | D01255A | G08 | | ALL |
| 317B | 22 | PC | MQ | | 4-0 | 27-41-21 | D00667B | | | | J03 | D01255A | G09 | | ALL |
| 317R | 22 | PC | MQ | | 0-0 | 27-41-21 | D00667B | | | | J02 | D01255A | H10 | | ALL |
| 317Y | 22 | PC | MQ | | 0-0 | 27-41-21 | D00667B | | | | J04 | D01255A | G10 | | ALL |
| 318B | 22 | PC | MR | | 4-0 | 27-41-21 | D00667B | | | | H03 | D01257A | H09 | | ALL |
| 318R | 22 | PC | MR | | 0-0 | 27-41-21 | D00667B | | | | H02 | D01257A | H08 | | ALL |
| 318Y | 22 | PC | MR | | 0-0 | 27-41-21 | D00667B | | | | H04 | D01257A | G08 | | ALL |
| 319B | 22 | PC | MS | | 4-0 | 27-41-21 | D00667B | | | | G03 | D01257A | G09 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0140
 Page 8
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0141 | 286T0141 | | | E2-1 SHELF (continued) | | | | | | | | | | | | |
| 319R | 22 | PC | MS | 0-0 | 27-41-21 | D00667B | G02 | | | D01257A | H10 | | | ALL | | |
| 319Y | 22 | PC | MS | 0-0 | 27-41-21 | D00667B | G04 | | | D01257A | G10 | | | ALL | | |
| 503 | 22 | PA | | 2-0 | 22-21-21 | D01261A | CAP | Y | | GDX0008 | D.. | 2 | | 150-199, 275-299 | | |
| 504 | 22 | PA | | 2-0 | 22-21-21 | D01261A | CAP | Y | | GDX0008 | D.. | 2 | | 150-199, 275-299 | | |
| 601 | 24 | PK | | 4-0 | 27-32-21 | D04363J | | | 42 | D00831B | H12 | | | ALL | | |
| 602 | 20 | PA | | 2-0 | 27-32-21 | D04363J | | | 43 | GDX0008 | S.. | 2 | | ALL | | |
| 603Y | 22 | PJ | | 3-0 | 27-41-21 | D11812 | | | A2 | D05139J | | 10 | | ALL | | |
| 604 | 22 | PA | | 3-0 | 27-41-21 | D11812 | | | X2 | D04363J | | 16 | | ALL | | |
| 605 | 22 | PA | | 4-0 | 27-41-21 | D11812 | | | X1 | TB0141G | | 83 | 2 | ALL | | |
| 606Y | 22 | PJ | | 3-0 | 27-41-21 | D11812 | | | A1 | D04363J | | 5 | | 050-099 | | |
| 606Y | 22 | PJ | | 3-0 | 27-41-21 | D11812 | | | A1 | D04363J | | 27 | | 150-199, 275-299 | | |
| 607Y | 22 | PJ | | 3-0 | 27-41-21 | D11812 | | | A3 | D04363J | | 27 | | 050-099 | | |
| 607Y | 22 | PJ | | 3-0 | 27-41-21 | D11812 | | | A3 | D04363J | | 5 | | 150-199, 275-299 | | |
| FRF | | | | 0-0 | 22-21-21 | D04363J | | | 9 | D04363J | | | | FF | ALL | |
| FRG | | | | 0-0 | 27-11-22 | D04363J | | | 25 | D04363J | | | | FG | ALL | |
| FRJ | | | | 0-0 | 22-22-21 | D04363J | | | 19 | D04363J | | | | FJ | ALL | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL | | | | | | | | | | | | |
| 002 | 24 | PK | | 5-4 | 34-12-22 | D04803J | | | 9 | D00468 | A2 | | | ALL | | |
| 004 | 24 | PK | | 6-3 | 34-12-22 | D03938 | | | A2 | D04803J | | 10 | | ALL | | |
| 008 | 16 | PA | | 4-8 | 23-34-11 | D05195J | | | 14 | K00458 | A2 | C | | 050-099, 275-278 | | |
| 008 | 16 | PA | | 4-8 | 23-34-11 | D05195J | | | 1 | K00458 | A2 | C | | 150-199, 280-299 | | |
| 009 | 16 | PA | | 4-7 | 23-34-11 | D05195J | | | 16 | K00458 | C2 | C | | 050-099 | | |
| 009 | 16 | PA | | 4-7 | 23-34-11 | D05195J | | | 2 | K00458 | C2 | C | | 150-199 | | |
| 009 | 16 | PA | | 6-0 | 23-34-11 | D05195J | | | 16 | K00458 | C2 | C | | 275-299 | | |
| 010 | 16 | PA | | 4-8 | 23-34-11 | D05195J | | | 24 | K00458 | A1 | C | | 050-099, 275-299 | | |
| 010 | 16 | PA | | 4-8 | 23-34-11 | D05195J | | | 3 | K00458 | A1 | C | | 150-199 | | |
| 011 | 16 | PA | | 4-7 | 23-34-11 | D05195J | | | 22 | K00458 | C1 | C | | 050-099, 275-299 | | |
| 011 | 16 | PA | | 4-7 | 23-34-11 | D05195J | | | 4 | K00458 | C1 | C | | 150-199 | | |
| 014 | 12 | PA | | 4-11 | 23-34-17 | D05195J | | | 18 | K00458 | B1 | C | | ALL | | |
| 015 | 10 | PA | | 4-7 | 23-34-19 | D05195J | | | 20 | K00458 | D1 | C | | 050-099, 150-199 | | |
| 015 | 10 | PA | | 6-0 | 23-34-19 | D05195J | | | 20 | K00458 | D1 | C | | 275-299 | | |
| 016 | 22 | PA | | 5-3 | 23-34-11 | D05195J | | | 8 | TB0196Y | A002 | BJ | | 050-099, 150-199 | | |
| 016 | 22 | PA | | 6-1 | 23-34-11 | D05195J | | | 8 | TB0196Y | A002 | BJ | | 275-299 | | |
| 017 | 24 | PK | | 7-2 | 32-09-13 | D05648J | | | 47 | TB0090Z | | 10 | BJ | 050-099, 150-199 | | |
| 017 | 24 | PK | | 7-5 | 32-09-13 | D05648J | | | 47 | TB0090Z | | 10 | BJ | 275-299 | | |
| 019 | 22 | PA | | 2-7 | 27-51-11 | D05668J | | | 2 | K00361 | X1 | C | | 050-099 | | |
| 019 | 22 | PA | | 3-0 | 27-51-11 | D05668J | | | 2 | K00361 | X1 | C | | 150-199, 275-299 | | |
| 01H | 20 | PA | | 4-8 | 30-71-22 | D05946J | | | 7 | TB0188Z | | 15 | BJ | 050-099 | | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | |
| 01J | 24 | | PK | | 6-10 | 21-26-11 | D05650J | | 9 | | TB0266X | A009 | BJ | | 156-157, 166-199 |
| 01J | 24 | | PK | | 7-2 | 21-26-11 | D05650J | | 9 | | TB0266X | A009 | BJ | | 277-299 |
| 020 | 22 | | PA | | 3-3 | 27-51-11 | D05668J | | 13 | | K00359 | | C | | 050-099 |
| 020 | 22 | | PA | | 4-0 | 27-51-11 | D05668J | | 13 | | K00359 | | C | | 150-199, 275-299 |
| 021 | 22 | | PA | | 3-7 | 27-51-11 | D05668J | | 14 | | K00360 | | C | | 050-099 |
| 021 | 22 | | PA | | 5-0 | 27-51-11 | D05668J | | 14 | | K00360 | | C | | 150-199, 275-299 |
| 022 | 18 | | PA | | 6-3 | 27-51-11 | D05668J | | 3 | DL | TB0188G | | 2 | | 050-099, 150-199 |
| 022 | 18 | | PA | | 6-8 | 27-51-11 | D05668J | | 3 | DL | TB0188G | | 2 | | 275-299 |
| 023 | 22 | | PA | | 5-4 | 30-71-21 | D05946J | | 11 | | TB0188Y | A004 | BJ | | 275-299 |
| 024 | 24 | | PK | | 1-10 | 33-16-14 | D06252J | | 4 | | D04803J | | | | ALL |
| 028 | 18 | | PA | | 1-11 | 25-29-11 | D05860J | | 10 | | D04928J | | | | ALL |
| 02A | 20 | | PA | | 2-4 | 73-21-12 | D03946 | | C3 | | GDX0002 | | 2 | | ALL |
| 02B | 22 | | PA | | 2-3 | 28-42-11 | D05890J | | 6 | | TB0200Y | C005 | BJ | | 050-099, 150-199 |
| 02B | 22 | | PA | | 2-8 | 28-42-11 | D05890J | | 6 | | TB0200Y | C005 | BJ | | 275-299 |
| 02C | 24 | | PK | | 3-6 | 28-42-11 | D05334J | | 11 | | TB0200Y | C005 | BJ | | 050-099, 150-199 |
| 02C | 24 | | PK | | 3-11 | 28-42-11 | D05334J | | 11 | | TB0200Y | C005 | BJ | | 275-299 |
| 02D | 20 | | PA | | 4-4 | 78-36-21 | M10439 | | B | C | GDX0002 | | 2 | | 050-099, 155-199, 275-299 |
| 02D | 20 | | PA | | 3-1 | 78-36-21 | M10439 | | B | C | GDX0002 | | 2 | | 150-154 |
| 02E | 22 | | PA | | 4-1 | 78-36-21 | M10439 | | A | C | D10162 | | | | 050-099, 155-199, 275-299 |
| 02E | 22 | | PA | | 1-11 | 78-36-21 | M10439 | | A | C | D10162 | | 2 | | 150-154 |
| 02F | 24 | | PK | | 7-9 | 78-36-21 | D05668J | | 24 | | TB0460Z | | BJ | | 050-099, 150-199 |
| 02F | 24 | | PK | | 7-11 | 78-36-21 | D05668J | | 24 | | TB0460Z | | BJ | | 275-299 |
| 02G | 24 | | PK | | 5-1 | 78-36-21 | D05840J | | 17 | | D10162 | | | | ALL |
| 02H | 24 | | PK | | 4-0 | 78-36-21 | TB0186Y | | A018 | BJ | D05334J | | | | 050-099, 150-199 |
| 02H | 24 | | PK | | 4-7 | 78-36-21 | TB0186Y | | A018 | BJ | D05334J | | | | 275-299 |
| 02J | 22 | | PA | | 4-11 | 78-36-21 | TB0186Y | | A018 | BJ | D05840J | | | | 050-099, 150-156, 162-166 |
| 02J | 24 | | PK | | 4-11 | 78-36-21 | TB0186Y | | A018 | BJ | D05840J | | | | 157, 167-199 |
| 02J | 22 | | PA | | 6-1 | 78-36-21 | TB0186Y | | A018 | BJ | D05840J | | | | 275-299 |
| 02K | 22 | | PA | | 6-2 | 78-36-21 | TB0186Y | | A018 | BJ | D10162 | | | | 050-099, 150-199 |
| 02K | 22 | | PA | | 6-9 | 78-36-21 | TB0186Y | | A018 | BJ | D10162 | | | | 275-299 |
| 02L | 24 | | PK | | 5-0 | 32-09-13 | D10184 | | A2 | | TB0188X | C007 | BJ | | 050-099, 150-199 |
| 02L | 24 | | PK | | 5-5 | 32-09-13 | D10184 | | A2 | | TB0188X | C007 | BJ | | 275-299 |
| 02M | 22 | | PQ | AS | 5-1 | 30-31-11 | D01396 | | C2 | | TB0188X | D007 | BJ | | 050-099, 150-199 |
| 02M | 22 | | PQ | AS | 6-0 | 30-31-11 | D01396 | | C2 | | TB0188X | D007 | BJ | | 275-299 |
| 02MZ | | | | AS | 0-0 | 30-31-11 | D01396 | | DED | | TB0188X | DED | | | ALL |
| 02N | 22 | | PQ | AT | 4-5 | 30-31-11 | D01396 | | C1 | | TB0196X | D004 | BJ | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11
Section W0140
Page 10
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|----|---|----------|----------|---------|----|-----|-------|---------|-------|---------|------|--------|-------|------------------|
| | | | | | Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 02N | 22 | PQ | AT | | 4-9 | 30-31-11 | D01396 | | C1 | | | | TB0196X | D004 | BJ | | 275-299 |
| 02NZ | | | AT | | 0-0 | 30-31-11 | D01396 | | DED | | | | TB0196X | DED | | | ALL |
| 02P | 24 | PK | | | 3-6 | 30-32-11 | D05334J | | 7 | | | | TB0200Y | A006 | BJ | | 050-099, 150-199 |
| 02P | 24 | PK | | | 3-11 | 30-32-11 | D05334J | | 7 | | | | TB0200Y | A006 | BJ | | 275-299 |
| 02Q | 22 | PA | | | 4-10 | 30-32-11 | D05908J | | 22 | | | | TB0200Y | A006 | BJ | | 050-099, 150-199 |
| 02Q | 22 | PA | | | 5-3 | 30-32-11 | D05908J | | 22 | | | | TB0200Y | A006 | BJ | | 275-299 |
| 02R | 22 | PQ | AC | | 4-10 | 30-32-11 | D00546 | | A3 | | | | TB0196Y | A007 | BJ | | 050-099, 150-199 |
| 02R | 22 | PQ | AC | | 5-4 | 30-32-11 | D00546 | | A3 | | | | TB0196Y | A007 | BJ | | 275-299 |
| 02RZ | | | AC | | 0-0 | 30-32-11 | D00546 | | DED | | | | TB0196Y | DED | | | ALL |
| 02S | 22 | PQ | AD | | 4-10 | 30-32-11 | D00546 | | A2 | | | | TB0196Y | C007 | BJ | | 050-099, 150-199 |
| 02S | 22 | PQ | AD | | 5-4 | 30-32-11 | D00546 | | A2 | | | | TB0196Y | C007 | BJ | | 275-299 |
| 02SZ | | | AD | | 0-0 | 30-32-11 | D00546 | | DED | | | | TB0196Y | DED | | | ALL |
| 02T | 24 | PK | | | 4-11 | 21-51-13 | D06252J | | 11 | | | | TB0196X | A016 | BJ | | 050-099, 150-199 |
| 02T | 24 | PK | | | 6-1 | 21-51-13 | D06252J | | 11 | | | | TB0196X | A016 | BJ | | 275-299 |
| 02U | 24 | PK | | | 4-9 | 21-51-13 | D05800J | | 2 | | | | TB0196X | B016 | BJ | | 050-099, 150-199 |
| 02U | 24 | PK | | | 5-4 | 21-51-13 | D05800J | | 2 | | | | TB0196X | B016 | BJ | | 275-299 |
| 02V | 24 | PK | | | 4-9 | 21-51-13 | D05800J | | 3 | | | | TB0196X | C016 | BJ | | 050-099, 150-199 |
| 02V | 24 | PK | | | 5-4 | 21-51-13 | D05800J | | 3 | | | | TB0196X | C016 | BJ | | 275-299 |
| 02Y | 24 | PK | | | 6-3 | 21-44-21 | D06252J | | 9 | | | | TB0188Z | 14 | BJ | | 050-099, 150-199 |
| 02Y | 24 | PK | | | 6-9 | 21-44-21 | D06252J | | 9 | | | | TB0188Z | 14 | BJ | | 275-299 |
| 02Z | 24 | PK | | | 6-0 | 21-26-21 | D10126 | | B3 | | | | D06252J | 5 | | | ALL |
| 031 | 18 | PA | | | 6-9 | 27-51-11 | D05668J | | 1 | DL | | | TB0090G | 15 | 2 | | 050-099, 150-199 |
| 031 | 18 | PA | | | 6-10 | 27-51-11 | D05668J | | 1 | DL | | | TB0090G | 15 | 2 | | 275-299 |
| 032 | 20 | PA | | | 6-2 | 27-51-11 | D05668J | | 4 | | | | TB0188G | 10 | 2 | | 050-099, 150-199 |
| 032 | 20 | PA | | | 6-8 | 27-51-11 | D05668J | | 4 | | | | TB0188G | 10 | 2 | | 275-299 |
| 033 | 22 | PA | | | 6-6 | 27-51-11 | D05668J | | 15 | | | | D03908 | X2 | | | ALL |
| 03J | 24 | PK | | | 6-3 | 21-44-21 | D06252J | | 6 | | | | TB0188Z | 14 | BJ | | 050-099, 150-199 |
| 03J | 24 | PK | | | 6-9 | 21-44-21 | D06252J | | 6 | | | | TB0188Z | 14 | BJ | | 275-299 |
| 03K | 22 | PA | | | 6-5 | 21-44-21 | D06252J | | 7 | | | | TB0186Y | A005 | BJ | | 050-099, 150-199 |
| 03K | 22 | PA | | | 6-9 | 21-44-21 | D06252J | | 7 | | | | TB0186Y | A005 | BJ | | 275-299 |
| 03L | 24 | PK | | | 6-0 | 21-26-21 | D10126 | | B2 | | | | D06252J | 8 | | | ALL |
| 03M | 24 | PK | | | 4-4 | 21-44-21 | D10126 | | C2 | | | | D05744J | 12 | | | ALL |
| 03N | 22 | PA | | | 4-9 | 21-44-21 | D05744J | | 32 | | | | D10460 | B3 | | | ALL |
| 03P | 22 | PA | | | 4-11 | 21-44-21 | D05744J | | 14 | | | | TB0090Y | C001 | BJ | | 050-099, 150-199 |
| 03P | 22 | PA | | | 5-5 | 21-44-21 | D05744J | | 14 | | | | TB0090Y | C001 | BJ | | 275-299 |
| 03Q | 24 | PK | | | 4-3 | 21-44-21 | D05334J | | 16 | | | | TB0186Y | A005 | BJ | | 050-099, 150-199 |
| 03Q | 24 | PK | | | 4-7 | 21-44-21 | D05334J | | 16 | | | | TB0186Y | A005 | BJ | | 275-299 |
| 03R | 24 | PK | | | 1-6 | 21-44-21 | D10126 | | C3 | | | | D10460 | B2 | | | ALL |
| 03S | 22 | PA | | | 1-8 | 21-44-21 | D10126 | | C1 | | | | TB0090Y | C001 | BJ | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | |
| 03S | 22 | | PA | | 2-2 | 21-44-21 | D10126 | | | | | | | | 275-299 |
| 03T | 22 | | PA | | 6-5 | 21-44-21 | D10460 | | | | | | | | 050-099, 150-199 |
| 03T | 22 | | PA | | 6-10 | 21-44-21 | D10460 | | | | | | | | 275-299 |
| 03U | 22 | | PA | | 1-10 | 21-44-21 | D10460 | | | | | | | | 050-099, 150-199 |
| 03U | 22 | | PA | | 2-4 | 21-44-21 | D10460 | | | | | | | | 275-299 |
| 03W | 24 | | PK | | 6-5 | 21-44-21 | D06252J | | | 10 | | | | | ALL |
| 03X | 24 | | PK | | 6-1 | 21-44-21 | D10460 | | | A1 | | | | | 050-099, 150-199 |
| 03X | 24 | | PK | | 6-10 | 21-44-21 | D10460 | | | A1 | | | | | 275-299 |
| 03Y | 24 | | PK | | 6-3 | 21-44-21 | D10460 | | | X1 | | | | | 050-099, 150-199 |
| 03Y | 24 | | PK | | 6-10 | 21-44-21 | D10460 | | | X1 | | | | | 275-299 |
| 03Z | 24 | | PK | | 4-4 | 21-44-11 | D05744J | | | 8 | | | | | ALL |
| 042 | 22 | | PA | | 1-11 | 33-51-11 | D05668J | | | 28 | | | | | ALL |
| 044 | 20 | | PA | | 5-5 | 30-71-23 | D05820J | | | 1 | | | | | 050-099, 150-199 |
| 044 | 22 | | PA | | 6-3 | 30-71-23 | D05820J | | | 1 | | | | | 275-299 |
| 045 | 22 | | PA | | 5-0 | 30-71-23 | D05820J | | | 5 | | | | | 150-154 |
| 045 | 20 | | PA | | 5-0 | 30-71-23 | D05820J | | | 5 | | | | | 155-199 |
| 045 | 22 | | PA | | 6-3 | 30-71-23 | D05820J | | | 5 | | | | | 275-299 |
| 046 | 22 | | PA | | 5-0 | 30-71-23 | D05820J | | | 2 | | | | | 150-154 |
| 046 | 20 | | PA | | 5-0 | 30-71-23 | D05820J | | | 2 | | | | | 155-199 |
| 046 | 22 | | PA | | 6-3 | 30-71-23 | D05820J | | | 2 | | | | | 275-299 |
| 047 | 20 | | PA | | 4-8 | 30-71-23 | D05690J | | | 31 | | | | | 050-099 |
| 047 | 22 | | PA | | 4-8 | 30-71-23 | D05820J | | | 3 | | | | | 150-154, 275-299 |
| 047 | 20 | | PA | | 4-8 | 30-71-23 | D05820J | | | 3 | | | | | 155-199 |
| 048 | 20 | | PA | | 5-5 | 30-71-23 | D05820J | | | 7 | | | | | 050-099, 150-199 |
| 048 | 22 | | PA | | 6-3 | 30-71-23 | D05820J | | | 7 | | | | | 275-299 |
| 04A | 24 | | PK | | 4-4 | 21-44-11 | D05744J | | | 9 | | | | | ALL |
| 04B | 20 | | PA | | 1-9 | 21-44-11 | GD0002 | | | D.. | 2 | | | | ALL |
| 04C | 24 | | PK | | 4-4 | 21-44-11 | D05744J | | | 13 | | | | | ALL |
| 04D | 24 | | PK | | 4-4 | 21-44-11 | D05744J | | | 11 | | | | | ALL |
| 04E | 24 | | PK | | 4-4 | 21-44-21 | D05744J | | | 34 | | | | | ALL |
| 04F | 24 | | PK | | 1-6 | 21-44-21 | D10460 | | | C1 | | | | | ALL |
| 04G | 24 | | PK | | 6-3 | 21-44-21 | D10460 | | | C2 | | | | | 050-099, 150-199 |
| 04G | 24 | | PK | | 6-10 | 21-44-21 | D10460 | | | C2 | | | | | 275-299 |
| 04J | 20 | | PA | | 4-8 | 30-71-22 | D05946J | | | 23 | | | | | 050-099 |
| 04K | 20 | | PA | | 2-10 | 30-71-22 | D05690J | | | 21 | | | | | 050-099 |
| 04L | 20 | | PA | | 2-10 | 30-71-22 | D05690J | | | 35 | | | | | 050-099 |
| 04M | 20 | | PA | | 2-10 | 30-71-22 | D05690J | | | 36 | | | | | 050-099 |
| 056 | 22 | | PA | | 6-7 | 27-51-11 | D05650J | | | 10 | | | | | 050-099, 150-199 |
| 056 | 22 | | PA | | 6-11 | 27-51-11 | D05650J | | | 10 | | | | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 12
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | |
| 057 | 18 | | PA | 6-6 | 27-51-11 | D05650J | 11 | DK | | TB0188G | 5 | 2 | | 050-099, 150-199 | | |
| 057 | 18 | | PA | 6-11 | 27-51-11 | D05650J | 11 | DK | | TB0188G | 5 | 2 | | 275-299 | | |
| 058 | 20 | | PA | 6-3 | 27-51-11 | D05650J | 12 | | | D10016 | A1 | | | ALL | | |
| 059 | 18 | | PA | 6-8 | 27-51-11 | D03908 | B1 | | | TB0188G | 5 | 2 | | 050-099, 150-199 | | |
| 059 | 18 | | PA | 7-1 | 27-51-11 | D03908 | B1 | | | TB0188G | 5 | 2 | | 275-299 | | |
| 05B | 22 | | PQ | 6-2 | 27-62-11 | D05668J | 37 | | | TB0186Y | A009 | BJ | | 050-099, 150-199 | | |
| 05B | 22 | | PQ | 6-8 | 27-62-11 | D05668J | 37 | | | TB0186Y | A009 | BJ | | 275-299 | | |
| 05BZ | | | BA | 0-0 | 27-62-11 | D05668J | DED | | | TB0186Y | DED | | | ALL | | |
| 05D | 24 | | PK | 6-5 | 22-41-11 | TB0188Z | 13 | BJ | | D04803J | 4 | | | 050-099, 150-199 | | |
| 05D | 24 | | PK | 7-0 | 22-41-11 | TB0188Z | 13 | BJ | | D04803J | 4 | | | 275-299 | | |
| 05E | 24 | | PK | 6-5 | 21-53-22 | TB0186X | C001 | BJ | | D03674 | A3 | | | 050-099, 150-199 | | |
| 05E | 24 | | PK | 6-9 | 21-53-22 | TB0186X | C001 | BJ | | D03674 | A3 | | | 275-299 | | |
| 05F | 24 | | PK | 4-11 | 21-53-22 | TB0196X | D015 | BJ | | D03674 | B3 | | | 050-099, 150-199 | | |
| 05F | 24 | | PK | 6-0 | 21-53-22 | TB0196X | D015 | BJ | | D03674 | B3 | | | 275-299 | | |
| 05G | 24 | | PK | 5-2 | 21-53-22 | TB0200X | C004 | BJ | | D03674 | C3 | | | 050-099, 150-199 | | |
| 05G | 24 | | PK | 6-0 | 21-53-22 | TB0200X | C004 | BJ | | D03674 | C3 | | | 275-299 | | |
| 05H | 24 | | PK | 4-10 | 21-53-22 | TB0196X | D016 | BJ | | D03674 | D3 | | | 050-099, 150-199 | | |
| 05H | 24 | | PK | 6-0 | 21-53-22 | TB0196X | D016 | BJ | | D03674 | D3 | | | 275-299 | | |
| 05I | 24 | | PK | 4-9 | 21-53-22 | TB0196X | A017 | BJ | | D03676 | A3 | | | 050-099, 150-199 | | |
| 05I | 24 | | PK | 5-5 | 21-53-22 | TB0196X | A017 | BJ | | D03676 | A3 | | | 275-299 | | |
| 05J | 24 | | PK | 4-9 | 21-53-22 | TB0196X | B017 | BJ | | D03676 | B3 | | | 050-099, 150-199 | | |
| 05J | 24 | | PK | 5-5 | 21-53-22 | TB0196X | B017 | BJ | | D03676 | B3 | | | 275-299 | | |
| 05K | 22 | | PA | 6-0 | 21-51-21 | D05668J | 35 | | | D03676 | D1 | | | ALL | | |
| 05L | 22 | | PA | 4-6 | 21-51-21 | D05744J | 31 | | | D03676 | D2 | | | ALL | | |
| 05M | 24 | | PK | 6-8 | 21-51-21 | D06252J | 14 | | | D10130 | 8 | | | ALL | | |
| 05N | 24 | | PK | 5-0 | 21-51-21 | D05744J | 18 | | | D10130 | 7 | | | ALL | | |
| 05P | 24 | | PK | 5-0 | 21-53-21 | D05744J | 17 | | | D10130 | 11 | | | ALL | | |
| 05Q | 20 | | PA | 2-7 | 21-53-21 | GDX0002 | D.. | 2 | | D10130 | 9 | | | ALL | | |
| 05R | 24 | | PK | 2-7 | 21-53-21 | TB0090Y | A002 | BJ | | D10130 | 6 | | | 050-099, 150-199 | | |
| 05R | 24 | | PK | 3-1 | 21-53-21 | TB0090Y | A002 | BJ | | D10130 | 6 | | | 275-299 | | |
| 05S | 24 | | PK | 2-7 | 21-53-21 | TB0090Y | C002 | BJ | | D10130 | 12 | | | 050-099, 150-199 | | |
| 05S | 24 | | PK | 3-1 | 21-53-21 | TB0090Y | C002 | BJ | | D10130 | 12 | | | 275-299 | | |
| 05T | 24 | | PK | 4-11 | 21-53-21 | TB0090Y | A002 | BJ | | D05744J | 24 | | | 050-099, 150-199 | | |
| 05T | 24 | | PK | 5-5 | 21-53-21 | TB0090Y | A002 | BJ | | D05744J | 24 | | | 275-299 | | |
| 05U | 24 | | PK | 4-6 | 21-53-21 | D03676 | A1 | | | D05744J | 25 | | | ALL | | |
| 05V | 24 | | PK | 4-6 | 21-53-21 | D03676 | B1 | | | D05744J | 26 | | | ALL | | |
| 05W | 24 | | PK | 1-8 | 21-53-21 | D03676 | X1 | | | TB0090Y | A002 | BJ | | 050-099, 150-199 | | |
| 05W | 24 | | PK | 2-1 | 21-53-21 | D03676 | X1 | | | TB0090Y | A002 | BJ | | 275-299 | | |
| 05X | 24 | | PK | 1-8 | 21-53-21 | D03676 | X2 | | | TB0090Y | C002 | BJ | | 050-099, 150-199 | | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | |
| 05X | 24 | | PK | | 2-1 | 21-53-21 | D03676 | | X2 | | | TB0090Y | C002 | BJ | | 275-299 |
| 05Y | 24 | | PK | | 6-5 | 21-53-21 | D05668J | | 34 | | | TB0090Y | C002 | BJ | | 050-099, 150-199 |
| 05Y | 24 | | PK | | 6-10 | 21-53-21 | D05668J | | 34 | | | TB0090Y | C002 | BJ | | 275-299 |
| 060 | 18 | | PA | | 2-6 | 27-51-11 | D03908 | | B2 | | | TB0090G | 15 | 2 | | 050-099, 150-199 |
| 060 | 18 | | PA | | 2-7 | 27-51-11 | D03908 | | B2 | | | TB0090G | 15 | 2 | | 275-299 |
| 061 | 22 | | PA | | 2-6 | 27-51-11 | D03908 | | X1 | | | TB0090G | 15 | 2 | | 050-099, 150-199 |
| 061 | 22 | | PA | | 2-7 | 27-51-11 | D03908 | | X1 | | | TB0090G | 15 | 2 | | 275-299 |
| 065 | 22 | | PA | | 1-10 | 23-34-11 | K00458 | | X1 | C | | TB0196D | C025 | 2 | | 050-099, 150-199 |
| 065 | 22 | | PA | | 3-0 | 23-34-11 | K00458 | | X1 | C | | TB0196D | C025 | 2 | | 275-299 |
| 066 | 22 | | PA | | 1-7 | 23-34-11 | K00458 | | X2 | C | | TB0196D | A025 | 2 | | 050-099, 150-199 |
| 066 | 22 | | PA | | 2-0 | 23-34-11 | K00458 | | X2 | C | | TB0196D | A025 | 2 | | 275-299 |
| 069 | 24 | | PK | | 5-3 | 32-09-13 | TB0188Y | | A003 | BJ | | D00624 | X2 | | | 050-099, 150-199 |
| 069 | 24 | | PK | | 6-1 | 32-09-13 | TB0188Y | | A003 | BJ | | D00624 | X2 | | | 275-299 |
| 06A | 24 | | PK | | 6-2 | 21-53-21 | D03676 | | A2 | | | D06252J | 17 | | | ALL |
| 06B | 24 | | PK | | 6-2 | 21-53-21 | D03676 | | B2 | | | D06252J | 18 | | | ALL |
| 06C | 24 | | PK | | 6-3 | 21-53-21 | D03674 | | A2 | | | D06252J | 19 | | | ALL |
| 06D | 24 | | PK | | 6-3 | 21-53-21 | D03674 | | B2 | | | D06252J | 20 | | | ALL |
| 06E | 24 | | PK | | 6-3 | 21-53-21 | D03674 | | C2 | | | D06252J | 21 | | | ALL |
| 06F | 24 | | PK | | 6-3 | 21-53-21 | D03674 | | D2 | | | D06252J | 22 | | | ALL |
| 06G | 24 | | PK | | 1-9 | 21-53-21 | D03674 | | X2 | | | TB0090Y | C002 | BJ | | 050-099, 150-199 |
| 06G | 24 | | PK | | 2-3 | 21-53-21 | D03674 | | X2 | | | TB0090Y | C002 | BJ | | 275-299 |
| 06H | 24 | | PK | | 1-9 | 21-53-21 | TB0090Y | | A002 | BJ | | D03674 | X1 | | | 050-099, 150-199 |
| 06H | 24 | | PK | | 2-3 | 21-53-21 | TB0090Y | | A002 | BJ | | D03674 | X1 | | | 275-299 |
| 06I | 24 | | PK | | 4-8 | 21-53-21 | D05744J | | 27 | | | D03674 | A1 | | | ALL |
| 06J | 24 | | PK | | 4-8 | 21-53-21 | D05744J | | 28 | | | D03674 | B1 | | | ALL |
| 06K | 24 | | PK | | 4-8 | 21-53-21 | D05744J | | 29 | | | D03674 | C1 | | | ALL |
| 06L | 24 | | PK | | 4-8 | 21-53-21 | D05744J | | 30 | | | D03674 | D1 | | | ALL |
| 06M | 24 | | PK | | 5-0 | 32-09-13 | D10184 | | A3 | | | TB0188Y | C009 | BJ | | 050-099, 150-199 |
| 06M | 24 | | PK | | 5-5 | 32-09-13 | D10184 | | A3 | | | TB0188Y | C009 | BJ | | 275-299 |
| 06N | 24 | | PK | | 6-2 | 21-51-13 | D06252J | | 12 | | | TB0188X | A017 | BJ | | 050-099, 150-199 |
| 06N | 24 | | PK | | 6-9 | 21-51-13 | D06252J | | 12 | | | TB0188X | A017 | BJ | | 275-299 |
| 06P | 24 | | PK | | 6-2 | 21-51-13 | D06252J | | 13 | | | TB0188X | B017 | BJ | | 050-099, 150-199 |
| 06P | 24 | | PK | | 6-9 | 21-51-13 | D06252J | | 13 | | | TB0188X | B017 | BJ | | 275-299 |
| 06Q | 24 | | PK | | 6-2 | 21-51-13 | D06252J | | 23 | | | TB0188X | C017 | BJ | | 050-099, 150-199 |
| 06Q | 24 | | PK | | 6-9 | 21-51-13 | D06252J | | 23 | | | TB0188X | C017 | BJ | | 275-299 |
| 06R | 22 | | PA | | 5-4 | 30-71-22 | TB0188Y | | C003 | BJ | | D05946J | 29 | | | 275-299 |
| 072 | 18 | | PA | | 2-6 | 28-22-11 | K00188 | | C2 | D | * | D00930 | X1 | | | 050-099 |
| 072 | 18 | | PA | | 3-0 | 28-22-11 | K00188 | | C2 | D | * | D00930 | X1 | | | 150-199, 275-299 |
| 073 | 24 | | PK | | 6-5 | 36-11-41 | D06252J | | 2 | | | TB0188X | D006 | BJ | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 14

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | |
| 073 | 24 | | PK | | 6-9 | 36-11-41 | D06252J | | 2 | | | TB0188X | D006 | BJ | | 275-299 |
| 078 | 20 | | PA | | 2-8 | 28-22-11 | K00188 | | X2 | C | | GDX0001 | D.. | 2 | | 050-099 |
| 078 | 20 | | PA | | 4-0 | 28-22-11 | K00188 | | X2 | C | | GDX0001 | D.. | 2 | | 150-199, 275-299 |
| 079 | 24 | | PK | | 6-1 | 32-09-13 | D00546 | | X2 | | | TB0188Y | C009 | BJ | | 050-099, 150-199 |
| 079 | 24 | | PK | | 6-6 | 32-09-13 | D00546 | | X2 | | | TB0188Y | C009 | BJ | | 275-299 |
| 07F | 24 | | PV | BN | 2-5 | 29-11-22 | M00299 | | A | C | | TB0188X | D017 | BJ | | 050-099, 155-199 |
| 07F | 24 | | PV | BN | 6-10 | 29-11-22 | M00299 | | A | C | | TB0188X | D017 | BJ | | 150-154 |
| 07F | 24 | | PV | BN | 3-3 | 29-11-22 | M00299 | | A | C | | TB0188X | D017 | BJ | | 275-299 |
| 07FZ | | | | BN | 0-0 | 29-11-22 | M00299 | | DED | | | TB0188X | DED | | | ALL |
| 07G | 24 | | PV | BO | 2-5 | 29-11-22 | M00299 | | A | C | | TB0188X | A018 | BJ | | 050-099, 155-199 |
| 07G | 24 | | PV | BO | 6-10 | 29-11-22 | M00299 | | A | C | | TB0188X | A018 | BJ | | 150-154 |
| 07G | 24 | | PV | BO | 3-3 | 29-11-22 | M00299 | | A | C | | TB0188X | A018 | BJ | | 275-299 |
| 07GZ | | | | BO | 0-0 | 29-11-22 | M00299 | | DED | | | TB0188X | DED | | | ALL |
| 07H | 22 | | PQ | BP | 3-0 | 29-11-22 | M00920 | | B | C | | TB0186D | A024 | 2 | | 050-099, 155-199 |
| 07H | 22 | | PQ | BP | 6-10 | 29-11-22 | M00920 | | B | C | | TB0186D | A024 | 2 | | 150-154 |
| 07H | 22 | | PQ | BP | 3-10 | 29-11-22 | M00920 | | B | C | | TB0186D | A024 | 2 | | 275-299 |
| 07HZ | | | | BP | 0-0 | 29-11-22 | M00920 | | DED | | | TB0186D | DED | | | ALL |
| 07J | 22 | | PQ | BQ | 1-2 | 27-09-13 | TB0186D | | C024 | 2 | | TB0188X | C018 | BJ | | 050-099, 150-199 |
| 07J | 22 | | PQ | BQ | 0-7 | 27-09-13 | TB0186D | | C024 | 2 | | TB0188X | C018 | BJ | | 275-299 |
| 07JZ | | | | BQ | 0-0 | 27-09-13 | TB0186D | | DED | | | TB0188X | DED | | | ALL |
| 07K | 24 | | PV | BR | 2-5 | 29-11-22 | M00300 | | A | C | | TB0188X | D018 | BJ | | 050-099, 155-199 |
| 07K | 24 | | PV | BR | 6-6 | 29-11-22 | M00300 | | A | C | | TB0188X | D018 | BJ | | 150-154 |
| 07K | 24 | | PV | BR | 3-1 | 29-11-22 | M00300 | | A | C | | TB0188X | D018 | BJ | | 275-299 |
| 07KZ | | | | BR | 0-0 | 29-11-22 | M00300 | | DED | | | TB0188X | DED | | | ALL |
| 07L | 24 | | PV | BS | 2-3 | 29-11-22 | M00300 | | B | C | | TB0186D | A025 | 2 | | 050-099, 155-199 |
| 07L | 24 | | PV | BS | 6-4 | 29-11-22 | M00300 | | B | C | | TB0186D | A025 | 2 | | 150-154 |
| 07L | 24 | | PV | BS | 3-1 | 29-11-22 | M00300 | | B | C | | TB0186D | A025 | 2 | | 275-299 |
| 07LZ | | | | BS | 0-0 | 29-11-22 | M00300 | | DED | | | TB0186D | DED | | | ALL |
| 07M | 22 | | PQ | BT | 1-2 | 27-09-13 | TB0186D | | C025 | 2 | | TB0188X | B019 | BJ | | 050-099, 150-199 |
| 07M | 22 | | PQ | BT | 0-7 | 27-09-13 | TB0186D | | C025 | 2 | | TB0188X | B019 | BJ | | 275-299 |
| 07MZ | | | | BT | 0-0 | 27-09-13 | TB0186D | | DED | | | TB0188X | DED | | | ALL |
| 07N | 24 | | PV | BU | 3-2 | 29-11-22 | M00500 | | A | C | | TB0188Y | C012 | BJ | | 050-099, 150-199 |
| 07N | 24 | | PV | BU | 3-9 | 29-11-22 | M00500 | | A | C | | TB0188Y | C012 | BJ | | 275-299 |
| 07NZ | | | | BU | 0-0 | 29-11-22 | M00500 | | DED | | | TB0188Y | DED | | | ALL |
| 07P | 24 | | PV | BV | 3-1 | 29-11-22 | M00500 | | A | C | | TB0186D | A019 | 2 | | 050-099, 150-199 |
| 07P | 24 | | PV | BV | 3-9 | 29-11-22 | M00500 | | A | C | | TB0186D | A019 | 2 | | 275-299 |
| 07PZ | | | | BV | 0-0 | 29-11-22 | M00500 | | DED | | | TB0186D | DED | | | ALL |
| 07Q | 24 | | PV | BW | 3-0 | 29-11-22 | M00500 | | B | C | | TB0188X | A020 | BJ | | 050-099, 150-199 |
| 07Q | 24 | | PV | BW | 3-9 | 29-11-22 | M00500 | | B | C | | TB0188X | A020 | BJ | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 15

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 07QZ | | | | BW | 0-0 | 29-11-22 | M00500 | | DED | | | | TB0188X | DED | | | ALL |
| 07S | 20 | PA | | | 4-2 | 29-11-22 | M00500 | | G | C | | | GDX0004 | D.. | 2 | | ALL |
| 07T | 22 | PA | | | 2-0 | 29-11-22 | TB0200D | | C025 | 2 | | | TB0186Y | C018 | BJ | | 050-099, 150-199 |
| 07T | 22 | PA | | | 2-10 | 29-11-22 | TB0200D | | C025 | 2 | | | TB0186Y | C018 | BJ | | 275-299 |
| 07U | 22 | PQ | CA | | 3-1 | 29-11-22 | M00924 | | A | C | | | TB0188X | A021 | BJ | | 050-099, 155-199 |
| 07U | 22 | PQ | CA | | 6-6 | 29-11-22 | M00924 | | A | C | | | TB0188X | A021 | BJ | | 150-154 |
| 07U | 22 | PQ | CA | | 3-9 | 29-11-22 | M00924 | | A | C | | | TB0188X | A021 | BJ | | 275-299 |
| 07UZ | | | | CA | 0-0 | 29-11-22 | M00924 | | DED | | | | TB0188X | DED | | | ALL |
| 07V | 22 | PQ | CB | | 3-1 | 29-11-22 | M00924 | | B | C | | | TB0188X | B021 | BJ | | 050-099, 155-199 |
| 07V | 22 | PQ | CB | | 6-6 | 29-11-22 | M00924 | | B | C | | | TB0188X | B021 | BJ | | 150-154 |
| 07V | 22 | PQ | CB | | 3-9 | 29-11-22 | M00924 | | B | C | | | TB0188X | B021 | BJ | | 275-299 |
| 07VZ | | | | CB | 0-0 | 29-11-22 | M00924 | | DED | | | | TB0188X | DED | | | ALL |
| 07W | 22 | PQ | CC | | 3-4 | 27-62-11 | M00963 | | A | C | | | TB0186Y | C005 | BJ | | 050-099, 155-199 |
| 07W | 22 | PQ | CC | | 7-1 | 27-62-11 | M00963 | | A | C | | | TB0186Y | C005 | BJ | | 150-154 |
| 07W | 22 | PQ | CC | | 3-8 | 27-62-11 | M00963 | | A | C | | | TB0186Y | C005 | BJ | | 275-299 |
| 07WZ | | | | CC | 0-0 | 27-62-11 | M00963 | | DED | | | | TB0186Y | DED | | | ALL |
| 07X | 22 | PQ | CD | | 3-3 | 27-62-11 | M00963 | | B | C | | | TB0186Y | A009 | BJ | | 050-099, 155-199 |
| 07X | 22 | PQ | CD | | 7-0 | 27-62-11 | M00963 | | B | C | | | TB0186Y | A009 | BJ | | 150-154 |
| 07X | 22 | PQ | CD | | 3-8 | 27-62-11 | M00963 | | B | C | | | TB0186Y | A009 | BJ | | 275-299 |
| 07XZ | | | | CD | 0-0 | 27-62-11 | M00963 | | DED | | | | TB0186Y | DED | | | ALL |
| 07Y | 24 | PV | CE | | 3-2 | 24-51-52 | M01084 | | B | C | | | TB0188X | D020 | BJ | | 050-099, 155-199 |
| 07Y | 24 | PV | CE | | 6-11 | 24-51-52 | M01084 | | B | C | | | TB0188X | D020 | BJ | | 150-154 |
| 07Y | 24 | PV | CE | | 3-10 | 24-51-52 | M01084 | | B | C | | | TB0188X | D020 | BJ | | 275-299 |
| 07YZ | | | | CE | 0-0 | 24-51-52 | M01084 | | DED | | | | TB0188X | DED | | | ALL |
| 080 | 24 | PK | | | 4-11 | 32-09-13 | D00546 | | X1 | | | | TB0196Z | 5 | BJ | | 050-099, 150-199 |
| 080 | 24 | PK | | | 5-4 | 32-09-13 | D00546 | | X1 | | | | TB0196Z | 5 | BJ | | 275-299 |
| 081 | 20 | PA | | | 3-0 | 30-71-21 | D05690J | | 37 | | | | TB0186Y | C012 | BJ | | 050-099, 155-199 |
| 081 | 22 | PA | | | 3-0 | 30-71-21 | D05690J | | 37 | | | | TB0186Y | C012 | BJ | | 150-154 |
| 081 | 22 | PA | | | 3-6 | 30-71-21 | D05690J | | 37 | | | | TB0186Y | C012 | BJ | | 275-299 |
| 084 | 20 | PA | | | 2-9 | 30-71-21 | TB0186Z | | 21 | BJ | | | D05690J | 35 | | | 150-199 |
| 08A | 20 | PA | | | 2-8 | 34-12-22 | D03910 | | C3 | | | | GDX0003 | D.. | 2 | | ALL |
| 08B | 24 | PK | | | 6-2 | 34-12-22 | D03910 | | A2 | | | | D04803J | 3 | | | ALL |
| 08C | 20 | PA | | | 2-4 | 34-12-22 | D00468 | | C3 | | | | GDX0003 | D.. | 2 | | ALL |
| 08E | 20 | PA | | | 2-9 | 34-12-22 | D03938 | | C3 | | | | GDX0003 | D.. | 2 | | ALL |
| 08F | 22 | PA | | | 4-11 | 21-44-21 | D05744J | | 33 | | | | TB0090Y | C001 | BJ | | 050-099, 150-199 |
| 08F | 22 | PA | | | 5-5 | 21-44-21 | D05744J | | 33 | | | | TB0090Y | C001 | BJ | | 275-299 |
| 08G | 24 | PK | | | 8-4 | 24-51-52 | TB0188X | | D020 | BJ | | | K00622 | X1 | L | | 050-099, 150-199 |
| 08G | 24 | PK | | | 9-0 | 24-51-52 | TB0188X | | D020 | BJ | | | K00622 | X1 | L | | 275-299 |
| 08H | 24 | PK | | | 7-11 | 24-51-52 | TB0196X | | C004 | BJ | | | K00622 | X2 | L | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 16

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|-------|---------|------|---------|---------|------|------|--------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | |
| 08H | 24 | | PK | 8-4 | 24-51-52 | TB0196X | C004 | BJ | | K00622 | X2 | L | | 275-299 | | |
| 08P | 18 | | PA | 6-2 | 30-71-21 | TB0196G | | 10 | 2 | TB0090H | 16 | 2 | | 050-099 | | |
| 08P | 18 | | PA | 6-2 | 30-71-21 | TB0090H | | 16 | 2 | TB0196G | 10 | 2 | | 150-199 | | |
| 08P | 22 | | PA | 7-5 | 30-71-21 | TB0090H | | 16 | 2 | TB0186Y | C011 | BJ | | 275-299 | | |
| 08Q | 24 | | PV | CJ | 1-6 | 29-11-22 | | M00299 | B | C | TB0200D | A025 | 2 | 050-099, 155-199 | | |
| 08Q | 24 | | PV | CJ | 6-0 | 29-11-22 | | M00299 | B | C | TB0200D | A025 | 2 | 150-154 | | |
| 08Q | 24 | | PV | CJ | 2-0 | 29-11-22 | | M00299 | B | C | TB0200D | A025 | 2 | 275-299 | | |
| 08QZ | | | | CJ | 0-0 | 29-11-22 | | M00299 | DED | | TB0200D | DED | | ALL | | |
| 08R | 22 | | PQ | CG | 1-2 | 29-11-22 | | TB0186D | C024 | 2 | TB0188X | B018 | BJ | 050-099, 150-199 | | |
| 08R | 22 | | PQ | CG | 0-7 | 29-11-22 | | TB0186D | C024 | 2 | TB0188X | B018 | BJ | 275-299 | | |
| 08RZ | | | | CG | 0-0 | 29-11-22 | | TB0186D | DED | | TB0188X | DED | | ALL | | |
| 08S | 24 | | PV | CH | 1-2 | 29-11-22 | | TB0186D | C025 | 2 | TB0188X | A019 | BJ | 050-099, 150-199 | | |
| 08S | 24 | | PV | CH | 0-7 | 29-11-22 | | TB0186D | C025 | 2 | TB0188X | A019 | BJ | 275-299 | | |
| 08SZ | | | | CH | 0-0 | 29-11-22 | | TB0186D | DED | | TB0188X | DED | | ALL | | |
| 091 | 24 | | PK | 4-6 | 36-11-41 | D05840J | | | 13 | TB0200X | C003 | BJ | | 050-099, 150-199 | | |
| 091 | 24 | | PK | 4-10 | 36-11-41 | D05840J | | | 13 | TB0200X | C003 | BJ | | 275-299 | | |
| 092 | 24 | | PK | 4-6 | 36-11-41 | D05840J | | | 14 | TB0200X | D003 | BJ | | 050-099, 150-199 | | |
| 092 | 24 | | PK | 4-10 | 36-11-41 | D05840J | | | 14 | TB0200X | D003 | BJ | | 275-299 | | |
| 093 | 24 | | PK | 4-6 | 36-11-41 | D05840J | | | 15 | TB0200X | A004 | BJ | | 050-099, 150-199 | | |
| 093 | 24 | | PK | 4-10 | 36-11-41 | D05840J | | | 15 | TB0200X | A004 | BJ | | 275-299 | | |
| 094 | 24 | | PK | 4-6 | 36-11-41 | D05840J | | | 16 | TB0200X | B004 | BJ | | 050-099, 150-199 | | |
| 094 | 24 | | PK | 4-10 | 36-11-41 | D05840J | | | 16 | TB0200X | B004 | BJ | | 275-299 | | |
| 095 | 22 | | PA | 2-4 | 30-11-11 | D12004 | | | X1 | TB0268Y | C006 | BJ | | 050-099, 150-199 | | |
| 095 | 22 | | PA | 2-8 | 30-11-11 | D12004 | | | X1 | TB0268Y | C006 | BJ | | 275-299 | | |
| 09B | 16 | | PA | 5-5 | 28-22-11 | K00188 | | | A1 | D | D05890J | 4 | | ALL | | |
| 09C | 16 | | PA | 5-5 | 28-22-11 | K00188 | | | B1 | D | D05890J | 7 | | ALL | | |
| 09D | 16 | | PA | 5-5 | 28-22-11 | K00188 | | | C1 | D | D05890J | 10 | | ALL | | |
| 09E | 16 | | PA | 6-4 | 28-22-11 | D05800J | | | 4 | | K00188 | A2 | D | ALL | | |
| 09F | 16 | | PA | 6-4 | 28-22-11 | D05800J | | | 7 | | K00188 | B2 | D | ALL | | |
| 09G | 16 | | PA | 6-4 | 28-22-11 | D05800J | | | 10 | | K00188 | C2 | D | * 050-099 | | |
| 09G | 16 | | PA | 7-0 | 28-22-11 | D05800J | | | 10 | | K00188 | C2 | D | * 150-199, 275-299 | | |
| 09H | 22 | | PQ | CK | 3-3 | 29-11-22 | | M00920 | A | C | TB0186X | C016 | BJ | 050-099, 155-199 | | |
| 09H | 22 | | PQ | CK | 7-0 | 29-11-22 | | M00920 | A | C | TB0186X | C016 | BJ | | 150-154 | |
| 09H | 22 | | PQ | CK | 3-10 | 29-11-22 | | M00920 | A | C | TB0186X | C016 | BJ | | 275-299 | |
| 09HZ | | | | CK | 0-0 | 29-11-22 | | M00920 | DED | | TB0186X | DED | | ALL | | |
| 09J | 22 | | PA | | 6-0 | 33-24-11 | | D05172J | 3 | | TB0200F | C002 | 2 | 050-099, 150-199 | | |
| 09J | 22 | | PA | | 6-4 | 33-24-11 | | D05172J | 3 | | TB0200F | C002 | 2 | 275-299 | | |
| 09L | 24 | | PK | | 2-10 | 30-34-21 | | D03946 | X1 | | TB0090Y | C011 | BJ | 275-299 | | |
| 09M | 22 | | PA | | 7-1 | 30-32-21 | | D05648J | 12 | | TB0090Y | A006 | BJ | 050-099, 150-199 | | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 17

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | |
| 09M | 22 | | PA | | 7-5 | 30-32-21 | D05648J | | | | | | | | 275-299 |
| 09Q | 20 | | PA | | 5-0 | 30-71-23 | D05820J | | | | | | | | 050-099, 150-199 |
| 09Q | 22 | | PA | | 6-3 | 30-71-23 | D05820J | | | | | | | | 275-299 |
| 09R | 20 | | PA | | 2-8 | 30-71-23 | D05690J | | | | | | | | 050-099 |
| 101 | 20 | | PA | | 4-8 | 30-71-21 | D05946J | | | | | | | | 050-099 |
| 101 | 20 | | PA | | 4-7 | 30-71-21 | D05946J | | | | | | | | 155-199 |
| 102 | 22 | | PA | | 5-2 | 52-11-11 | D05172J | | | | | | | | 050-099, 150-199 |
| 102 | 22 | | PA | | 6-4 | 52-11-11 | D05172J | | | | | | | | 275-299 |
| 103 | 22 | | PA | | 5-2 | 52-11-11 | D05172J | | | | | | | | 050-099, 150-199 |
| 103 | 22 | | PA | | 6-4 | 52-11-11 | D05172J | | | | | | | | 275-299 |
| 104 | 22 | | PA | | 5-2 | 52-11-11 | D05172J | | | | | | | | 050-099, 150-199 |
| 104 | 22 | | PA | | 6-4 | 52-11-11 | D05172J | | | | | | | | 275-299 |
| 105 | 18 | | PA | | 4-8 | 38-15-11 | D05820J | | 20 | DL | | | | | 050-099 |
| 105 | 18 | | PA | | 4-8 | 38-15-11 | D05820J | | 20 | DK | | | | | 150-199 |
| 105 | 18 | | PA | | 5-1 | 38-15-11 | D05820J | | 20 | DK | | | | | 275-299 |
| 106 | 18 | | PA | | 4-8 | 38-15-11 | D05820J | | 21 | DL | | | | | 050-099 |
| 106 | 18 | | PA | | 4-8 | 38-15-11 | D05820J | | 21 | DK | | | | | 150-199 |
| 106 | 18 | | PA | | 5-1 | 38-15-11 | D05820J | | 21 | DK | | | | | 275-299 |
| 107 | 18 | | PA | | 4-7 | 38-15-11 | D05820J | | 22 | DL | | | | | 050-099 |
| 107 | 18 | | PA | | 4-7 | 38-15-11 | D05820J | | 22 | DK | | | | | 150-199 |
| 107 | 18 | | PA | | 5-1 | 38-15-11 | D05820J | | 22 | DK | | | | | 275-299 |
| 108 | 20 | | PA | | 5-2 | 33-31-11 | D05650J | | 2 | | | | | | 050-099, 150-199 |
| 108 | 20 | | PA | | 6-2 | 33-31-11 | D05650J | | 2 | | | | | | 275-299 |
| 109 | 18 | | PA | | 4-7 | 30-71-11 | D05820J | | 9 | DK | | | | | 050-099, 150-199 |
| 109 | 18 | | PA | | 5-1 | 30-71-11 | D05820J | | 9 | DK | | | | | 275-299 |
| 10D | 22 | | PQ | AJ | 4-10 | 28-22-31 | D05744J | | 38 | | | | | | 050-099 |
| 10D | 22 | | PQ | PL | 4-10 | 28-22-31 | D05744J | | 38 | | | | | | 150-199, 275-299 |
| 10DZ | | | | AJ | 0-0 | 28-22-31 | D05744J | | DED | | | | | | 050-099 |
| 10DZ | | | | PL | 0-0 | 28-22-31 | D05744J | | DED | | | | | | 150-199, 275-299 |
| 10F | 22 | | PQ | BL | 5-2 | 28-22-31 | D05744J | | 15 | | | | | | 050-099, 150-199 |
| 10F | 22 | | PQ | BL | 5-5 | 28-22-31 | D05744J | | 15 | | | | | | 275-299 |
| 10FZ | | | | BL | 0-0 | 28-22-31 | D05744J | | DED | | | | | | ALL |
| 10G | 22 | | PQ | CL | 4-10 | 28-22-31 | D05744J | | 39 | | | | | | ALL |
| 10GZ | | | | CL | 0-0 | 28-22-31 | D05744J | | DED | | | | | | ALL |
| 10H | 20 | | PQ | DL | 4-1 | 28-22-31 | D05744J | | 36 | | | | | | ALL |
| 10HZ | | | | DL | 0-0 | 28-22-31 | D05744J | | DED | | | | | | ALL |
| 10I | 20 | | PQ | EL | 4-1 | 28-22-31 | D05744J | | 37 | | | | | | ALL |
| 10IZ | | | | EL | 0-0 | 28-22-31 | D05744J | | DED | | | | | | ALL |
| 10J | 20 | | PQ | FL | 2-3 | 28-22-31 | D02985 | | 3 | | | | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11
Section W0140
Page 18
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | |
| 10J | 20 | PQ | FL | 3-0 | 28-22-31 | D02985 | | 3 | | | GDX0004 | D.. | 2 | | 275-299 | |
| 10JZ | | | FL | 0-0 | 28-22-31 | D02985 | | DED | | | GDX0004 | DED | | | ALL | |
| 10K | 22 | PQ | GL | 2-8 | 28-22-31 | D02985 | | 13 | | | TB0090Y | A012 | BJ | | 050-099, 150-199 | |
| 10K | 22 | PQ | GL | 2-11 | 28-22-31 | D02985 | | 13 | | | TB0090Y | A012 | BJ | | 275-299 | |
| 10KZ | | | GL | 0-0 | 28-22-31 | D02985 | | DED | | | TB0090Y | DED | | | ALL | |
| 10L | 22 | PQ | HL | 11-2 | 28-22-31 | D02985 | | 7 | | | TB0268Y | A005 | BJ | | 050-099, 150-199 | |
| 10L | 22 | PQ | HL | 12-0 | 28-22-31 | D02985 | | 7 | | | TB0268Y | A005 | BJ | | 275-299 | |
| 10LZ | | | HL | 0-0 | 28-22-31 | D02985 | | DED | | | TB0268Y | DED | | | ALL | |
| 10M | 22 | PQ | IL | 11-1 | 28-22-31 | D02985 | | 5 | | | TB0268Y | C009 | BJ | | 050-099, 150-199 | |
| 10M | 22 | PQ | IL | 12-0 | 28-22-31 | D02985 | | 5 | | | TB0268Y | C009 | BJ | | 275-299 | |
| 10MZ | | | IL | 0-0 | 28-22-31 | D02985 | | DED | | | TB0268Y | DED | | | ALL | |
| 10N | 20 | PQ | JL | 2-3 | 28-22-31 | D02985 | | 1 | | | GDX0004 | D.. | 2 | | 050-099, 150-199 | |
| 10N | 20 | PQ | JL | 3-0 | 28-22-31 | D02985 | | 1 | | | GDX0004 | D.. | 2 | | 275-299 | |
| 10NZ | | | JL | 0-0 | 28-22-31 | D02985 | | DED | | | GDX0004 | DED | | | ALL | |
| 10P | 22 | PQ | QL | 4-8 | 28-22-31 | D05334J | | 23 | | | TB0090Y | A012 | BJ | | 050-099, 150-199 | |
| 10P | 22 | PQ | QL | 6-0 | 28-22-31 | D05334J | | 23 | | | TB0090Y | A012 | BJ | | 275-299 | |
| 10PZ | | | QL | 0-0 | 28-22-31 | D05334J | | DED | | | TB0090Y | DED | | | ALL | |
| 10R | 20 | PQ | KL | 2-3 | 28-22-31 | D02985 | | 12 | | | GDX0004 | D.. | 2 | | 050-099, 150-199 | |
| 10R | 20 | PQ | KL | 3-0 | 28-22-31 | D02985 | | 12 | | | GDX0004 | D.. | 2 | | 275-299 | |
| 10RZ | | | KL | 0-0 | 28-22-31 | D02985 | | DED | | | GDX0004 | DED | | | ALL | |
| 10S | 22 | PQ | ML | 9-6 | 28-22-31 | D05334J | | 24 | | | TB0268X | C002 | BJ | | 050-099, 150-199 | |
| 10S | 22 | PQ | ML | 9-0 | 28-22-31 | D05334J | | 24 | | | TB0268X | C002 | BJ | | 275-299 | |
| 10SZ | | | ML | 0-0 | 28-22-31 | D05334J | | DED | | | TB0268X | DED | | | ALL | |
| 10T | 22 | PQ | NL | 8-3 | 28-22-31 | D05890J | | 3 | | | TB0268X | D002 | BJ | | 050-099, 150-199 | |
| 10T | 22 | PQ | NL | 9-0 | 28-22-31 | D05890J | | 3 | | | TB0268X | D002 | BJ | | 275-299 | |
| 10TZ | | | NL | 0-0 | 28-22-31 | D05890J | | DED | | | TB0268X | DED | | | ALL | |
| 110 | 20 | PA | | 4-7 | 30-71-11 | D05820J | | 10 | | | TB0200F | C010 | 2 | | 050-099, 150-199 | |
| 110 | 20 | PA | | 5-1 | 30-71-11 | D05820J | | 10 | | | TB0200F | C010 | 2 | | 275-299 | |
| 111 | 24 | PK | | 5-3 | 33-21-11 | D05172J | | 10 | | | TB0200F | C011 | 2 | | 050-099, 150-199 | |
| 111 | 24 | PK | | 6-4 | 33-21-11 | D05172J | | 10 | | | TB0200F | C011 | 2 | | 275-299 | |
| 112 | 22 | PA | | 5-3 | 33-22-41 | D05172J | | 14 | | | TB0200F | A012 | 2 | | 050-099, 150-199 | |
| 112 | 22 | PA | | 6-4 | 33-22-41 | D05172J | | 14 | | | TB0200F | A012 | 2 | | 275-299 | |
| 113 | 20 | PA | | 5-3 | 33-22-42 | D05172J | | 16 | | | TB0200F | C012 | 2 | | 050-099, 150-199 | |
| 113 | 20 | PA | | 6-4 | 33-22-42 | D05172J | | 16 | | | TB0200F | C012 | 2 | | 275-299 | |
| 114 | 20 | PA | | 5-3 | 33-22-11 | D05172J | | 5 | | | TB0200F | A013 | 2 | | 050-099, 150-199 | |
| 114 | 20 | PA | | 6-4 | 33-22-11 | D05172J | | 5 | | | TB0200F | A013 | 2 | | 275-299 | |
| 115 | 20 | PA | | 5-3 | 33-27-11 | D05172J | | 2 | | | TB0200F | C013 | 2 | | 050-099, 150-199 | |
| 115 | 20 | PA | | 6-4 | 33-27-11 | D05172J | | 2 | | | TB0200F | C013 | 2 | | 275-299 | |
| 116 | 24 | PK | | 5-3 | 33-21-31 | D05172J | | 6 | | | TB0200F | A014 | 2 | | 050-099, 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 19

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 116 | 24 | | PK | 6-4 | 33-21-31 | D05172J | | 6 | | | | | TB0200F | A014 | 2 | | 275-299 |
| 117 | 24 | | PK | 5-3 | 77-35-11 | D04803J | | 1 | | | | | TB0200F | C014 | 2 | | 050-099, 150-199 |
| 117 | 24 | | PK | 6-4 | 77-35-11 | D04803J | | 1 | | | | | TB0200F | C014 | 2 | | 275-299 |
| 118 | 18 | | PA | 5-4 | 33-31-11 | D05648J | | 4 | DK | | | | TB0200F | A015 | 2 | | 050-099 |
| 118 | 18 | | PA | 5-4 | 33-31-11 | D05648J | | 4 | DL | | | | TB0200F | A015 | 2 | | 150-199 |
| 118 | 18 | | PA | 6-6 | 33-31-11 | D05648J | | 4 | DL | | | | TB0200F | A015 | 2 | | 275-299 |
| 119 | 22 | | PA | 5-2 | 33-24-11 | D05172J | | 7 | | | | | TB0200F | C016 | 2 | | 050-099 |
| 119 | 16 | | PA | 5-2 | 33-24-11 | D05172J | | 7 | FM | | | | TB0200F | C016 | 2 | | 150-199 |
| 119 | 16 | | PA | 6-4 | 33-24-11 | D05172J | | 7 | FM | | | | TB0200F | C016 | 2 | | 275-299 |
| 11L | 24 | | PK | 7-2 | 78-36-21 | D05840J | | 23 | | | | | TB0460Z | 7 | BJ | | 050-099, 150-199 |
| 11L | 24 | | PK | 7-4 | 78-36-21 | D05840J | | 23 | | | | | TB0460Z | 7 | BJ | | 275-299 |
| 11M | 24 | | PK | 7-0 | 78-36-21 | D05840J | | 8 | | | | | TB0460D | C013 | 2 | | 050-099, 150-199 |
| 11M | 24 | | PK | 7-4 | 78-36-21 | D05840J | | 8 | | | | | TB0460D | C013 | 2 | | 275-299 |
| 11N | 24 | | PK | 7-1 | 78-36-21 | D05840J | | 9 | | | | | TB0460X | B009 | BJ | | 050-099, 150-199 |
| 11N | 24 | | PK | 7-4 | 78-36-21 | D05840J | | 9 | | | | | TB0460X | B009 | BJ | | 275-299 |
| 11P | 24 | | PK | 7-1 | 78-36-21 | D05840J | | 10 | | | | | TB0460X | A010 | BJ | | 050-099, 150-199 |
| 11P | 24 | | PK | 7-4 | 78-36-21 | D05840J | | 10 | | | | | TB0460X | A010 | BJ | | 275-299 |
| 11Q | 20 | | PA | 2-9 | 78-34-11 | D00660 | | D3 | | | | | GDX0001 | D.. | 2 | | ALL |
| 11R | 24 | | PK | 7-0 | 78-36-21 | D05840J | | 11 | | | | | TB0460D | C014 | 2 | | 050-099, 150-199 |
| 11R | 24 | | PK | 7-4 | 78-36-21 | D05840J | | 11 | | | | | TB0460D | C014 | 2 | | 275-299 |
| 11T | 24 | | PK | 7-1 | 78-36-21 | D05840J | | 12 | | | | | TB0460X | C009 | BJ | | 050-099, 150-199 |
| 11T | 24 | | PK | 7-4 | 78-36-21 | D05840J | | 12 | | | | | TB0460X | C009 | BJ | | 275-299 |
| 11V | 24 | | PK | 7-1 | 78-36-21 | D05840J | | 18 | | | | | TB0460X | A009 | BJ | | 050-099, 150-199 |
| 11V | 24 | | PK | 7-4 | 78-36-21 | D05840J | | 18 | | | | | TB0460X | A009 | BJ | | 275-299 |
| 11W | 24 | | PK | 7-10 | 78-36-21 | D10162 | | 7 | | | | | TB0460Z | 7 | BJ | | 050-099, 150-199 |
| 11W | 24 | | PK | 8-0 | 78-36-21 | D10162 | | 7 | | | | | TB0460Z | 7 | BJ | | 275-299 |
| 11X | 20 | | PQ | GA | 2-10 | 78-34-11 | | D2 | | | | | TB0266X | C009 | BJ | | 050-099, 150-199 |
| 11X | 20 | | PQ | GA | 3-1 | 78-34-11 | | D2 | | | | | TB0266X | C009 | BJ | | 275-299 |
| 11XZ | | | GA | 0-0 | 78-34-11 | D00660 | | DED | | | | | TB0266X | | | AA | ALL |
| 11Y | 20 | | PQ | GB | 2-10 | 78-34-11 | | D1 | | | | | TB0266X | D009 | BJ | | 050-099, 150-199 |
| 11Y | 20 | | PQ | GB | 3-1 | 78-34-11 | | D1 | | | | | TB0266X | D009 | BJ | | 275-299 |
| 11YZ | | | GB | 0-0 | 78-34-11 | D00660 | | DED | | | | | TB0266X | | | AA | ALL |
| 120 | 22 | | PA | 5-2 | 33-24-11 | D05172J | | 8 | | | | | TB0200F | A016 | 2 | | 050-099 |
| 120 | 16 | | PA | 5-2 | 33-24-11 | D05172J | | 22 | FM | | | | TB0200F | A016 | 2 | | 150-199 |
| 120 | 16 | | PA | 6-4 | 33-24-11 | D05172J | | 22 | FM | | | | TB0200F | A016 | 2 | | 275-299 |
| 121 | 16 | | PA | 5-3 | 33-31-41 | D05648J | | 40 | | | | | TB0200G | 19 | 2 | | 050-099, 150-199 |
| 121 | 16 | | PA | 6-6 | 33-31-41 | D05648J | | 40 | | | | | TB0200G | 19 | 2 | | 275-299 |
| 122 | 18 | | PA | 5-3 | 33-31-41 | D05648J | | 56 | | | | | TB0200G | 19 | 2 | | 050-099, 150-199 |
| 122 | 18 | | PA | 6-6 | 33-31-41 | D05648J | | 56 | | | | | TB0200G | 19 | 2 | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 20
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | | |
| 123 | 20 | | PA | | 5-5 | 33-22-11 | D05172J | | 4 | | | | | TB0196X | B003 | BJ | | 050-099, 150-199 |
| 123 | 20 | | PA | | 6-4 | 33-22-11 | D05172J | | 4 | | | | | TB0196X | B003 | BJ | | 275-299 |
| 124 | 22 | | PA | | 5-2 | 33-24-11 | D05172J | | 9 | | | | | TB0200F | A018 | 2 | | 050-099 |
| 124 | 16 | | PA | | 5-2 | 33-24-11 | D05172J | | 24 | FM | | | | TB0200F | A018 | 2 | | 150-199 |
| 124 | 16 | | PA | | 6-4 | 33-24-11 | D05172J | | 24 | FM | | | | TB0200F | A018 | 2 | | 275-299 |
| 125 | 22 | | PA | | 5-2 | 33-22-21 | D05172J | | 1 | | | | | TB0200F | C015 | 2 | | 050-099, 150-199 |
| 125 | 22 | | PA | | 6-4 | 33-22-21 | D05172J | | 1 | | | | | TB0200F | C015 | 2 | | 275-299 |
| 126 | 20 | | PA | | 5-4 | 33-11-14 | D05648J | | 10 | | | | | TB0200F | C018 | 2 | | 050-099, 150-199 |
| 126 | 20 | | PA | | 6-6 | 33-11-14 | D05648J | | 10 | | | | | TB0200F | C018 | 2 | | 275-299 |
| 12E | 20 | | PQ | AL | 7-10 | 78-34-21 | D05800J | | 5 | | | | | TB0460X | A001 | BJ | | ALL |
| 12EZ | | | | AL | 0-0 | 78-34-21 | D05800J | | 12 | | | | | TB0460X | C002 | BJ | | ALL |
| 12F | 20 | | PA | | 7-10 | 78-34-21 | D05800J | | 8 | | | | | TB0460X | B001 | BJ | | ALL |
| 12G | 20 | | PQ | XO | 7-9 | 78-34-21 | D05668J | | 33 | | | | | TB0460Z | 8 | BJ | | 050-099, 150-199 |
| 12G | 20 | | PQ | XO | 7-11 | 78-34-21 | D05668J | | 33 | | | | | TB0460Z | 8 | BJ | | 275-299 |
| 12GZ | | | | XO | 0-0 | 78-34-21 | D05668J | | | | AC | | | TB0460Z | | | AB | ALL |
| 12H | 20 | | PQ | XP | 7-9 | 78-34-21 | TB0460Y | A006 | BJ | | | | | D05668J | 41 | | | 050-099, 150-199 |
| 12H | 20 | | PQ | XP | 7-11 | 78-34-21 | TB0460Y | A006 | BJ | | | | | D05668J | 41 | | | 275-299 |
| 12HZ | | | | XP | 0-0 | 78-34-21 | TB0460Y | | | | AD | | | D05668J | | | AC | ALL |
| 12J | 20 | | PQ | XQ | 7-9 | 78-34-21 | TB0460Y | C006 | BJ | | | | | D05668J | 17 | | | 050-099, 150-199 |
| 12J | 20 | | PQ | XQ | 7-11 | 78-34-21 | TB0460Y | C006 | BJ | | | | | D05668J | 17 | | | 275-299 |
| 12JZ | | | | XQ | 0-0 | 78-34-21 | TB0460Y | | | | AD | | | D05668J | | | AC | ALL |
| 12K | 20 | | PA | | 2-1 | 78-34-21 | TB0460Y | | | | AD | | | GDX0015 | S.. | 2 | | ALL |
| 136 | 22 | | PA | | 4-6 | 27-51-11 | D03908 | | A1 | | | | | D05334J | 18 | | | ALL |
| 137 | 20 | | PA | | 1-1 | 27-51-11 | D03908 | | A2 | | | | | GDX0001 | D.. | 2 | | ALL |
| 138 | 20 | | PA | | 5-0 | 30-71-23 | D05820J | | 13 | | | | | TB0188Z | 24 | BJ | | 050-099, 150-199 |
| 138 | 22 | | PA | | 6-3 | 30-71-23 | D05820J | | 13 | | | | | TB0188Z | 23 | BJ | | 275-299 |
| 13K | 22 | | PA | | 7-2 | 78-36-21 | D05840J | | 19 | | | | | TB0460Z | 7 | BJ | | 050-099, 150-199 |
| 13K | 22 | | PA | | 7-4 | 78-36-21 | D05840J | | 19 | | | | | TB0460Z | 7 | BJ | | 275-299 |
| 13M | 22 | | PA | | 7-0 | 78-36-21 | D05840J | | 21 | | | | | TB0460D | A014 | 2 | | 050-099, 150-199 |
| 13M | 22 | | PA | | 7-4 | 78-36-21 | D05840J | | 21 | | | | | TB0460D | A014 | 2 | | 275-299 |
| 13N | 22 | | PA | | 7-0 | 78-36-21 | D05840J | | 22 | | | | | TB0460D | A013 | 2 | | 050-099, 150-199 |
| 13N | 22 | | PA | | 7-4 | 78-36-21 | D05840J | | 22 | | | | | TB0460D | A013 | 2 | | 275-299 |
| 13P | 20 | | PA | | 7-10 | 78-34-21 | D05800J | | 6 | | | | | TB0460X | C001 | BJ | | ALL |
| 13Q | 20 | | PA | | 2-1 | 78-34-21 | TB0460Z | | | | AB | | | GDX0015 | S.. | 2 | | ALL |
| 143 | 24 | | PK | | 2-8 | 32-09-13 | D00624 | | X1 | | | | | TB0090Z | 10 | BJ | | 050-099, 150-199 |
| 143 | 24 | | PK | | 2-11 | 32-09-13 | D00624 | | X1 | | | | | TB0090Z | 10 | BJ | | 275-299 |
| 144 | 20 | | PA | | 8-9 | 30-71-22 | TB0090Y | A003 | BJ | | | | | C01158 | 1 | D | | 150-154 |
| 145 | 24 | | PK | | 3-0 | 32-09-13 | D00628 | | X1 | | | | | TB0090Z | 10 | BJ | | 050-099, 150-199 |
| 145 | 24 | | PK | | 3-3 | 32-09-13 | D00628 | | X1 | | | | | TB0090Z | 10 | BJ | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 21

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 146 | 24 | | PK | 6-1 | 32-09-13 | D00628 | | X2 | | | | | TB0188Y | A003 | BJ | | 050-099, 150-199 |
| 146 | 24 | | PK | 6-5 | 32-09-13 | D00628 | | X2 | | | | | TB0188Y | A003 | BJ | | 275-299 |
| 147 | 24 | | PK | 2-11 | 32-09-13 | D00630 | | X1 | | | | | TB0090Z | 10 | BJ | | 050-099, 150-199 |
| 147 | 24 | | PK | 3-2 | 32-09-13 | D00630 | | X1 | | | | | TB0090Z | 10 | BJ | | 275-299 |
| 148 | 24 | | PK | 3-0 | 32-09-13 | D00630 | | X2 | | | | | TB0090Y | C013 | BJ | | 050-099, 150-199 |
| 148 | 24 | | PK | 3-2 | 32-09-13 | D00630 | | X2 | | | | | TB0090Y | C013 | BJ | | 275-299 |
| 150 | 20 | | PA | 2-9 | 32-09-13 | D00630 | | D2 | | | | | GDX0002 | D.. | 2 | | ALL |
| 151 | 24 | | PK | 2-11 | 32-09-13 | D00660 | | X2 | | | | | TB0090Y | C013 | BJ | | 050-099, 150-199 |
| 151 | 24 | | PK | 3-0 | 32-09-13 | D00660 | | X2 | | | | | TB0090Y | C013 | BJ | | 275-299 |
| 152 | 24 | | PK | 2-9 | 32-09-13 | D00660 | | X1 | | | | | TB0090Z | 10 | BJ | | 050-099, 150-199 |
| 152 | 24 | | PK | 3-0 | 32-09-13 | D00660 | | X1 | | | | | TB0090Z | 10 | BJ | | 275-299 |
| 154 | 24 | | PK | 5-5 | 32-09-13 | D00630 | | D1 | | | | | TB0188X | B007 | BJ | | 050-099, 150-199 |
| 154 | 24 | | PK | 6-4 | 32-09-13 | D00630 | | D1 | | | | | TB0188X | B007 | BJ | | 275-299 |
| 155 | 20 | | PA | 6-5 | 30-71-21 | D03966 | | B1 | | | | | TB0186Y | C020 | BJ | | 050-099 |
| 155 | 20 | | PA | 6-5 | 30-71-21 | TB0186Z | | 20 | BJ | | | | D03966 | B1 | | | 150-199 |
| 157 | 20 | | PA | 4-8 | 30-71-21 | TB0186Z | | 20 | BJ | | | | D05946J | 34 | | | 150-199 |
| 158 | 20 | | PA | 4-8 | 30-71-21 | TB0186Z | | 20 | BJ | | | | D05946J | 35 | | | 150-199 |
| 159 | 20 | | PA | 4-8 | 30-71-21 | TB0186Z | | 20 | BJ | | | | D05946J | 36 | | | 150-199 |
| 161 | 20 | | PA | 4-8 | 30-71-21 | TB0186Z | | 20 | BJ | | | | D05946J | 38 | | | 150-199 |
| 162 | 20 | | PA | 2-10 | 30-71-21 | D05690J | | 23 | | | | | TB0186Y | A020 | BJ | | 050-099 |
| 162 | 20 | | PA | 3-2 | 30-71-21 | D05690J | | 23 | | | | | TB0188Y | C002 | BJ | | 150-199 |
| 163 | 20 | | PA | 8-8 | 30-71-24 | C01166 | | 1 | D | | | | D06252J | 24 | | | 050-099, 150-199 |
| 164 | 20 | | PA | 5-0 | 30-71-21 | D05946J | | 32 | | | | | TB0188Y | A004 | BJ | | 050-099 |
| 164 | 20 | | PA | 5-0 | 30-71-21 | TB0188Y | | A004 | BJ | | | | D05946J | 32 | | | 150-154 |
| 164 | 20 | | PA | 4-7 | 30-71-21 | TB0186Z | | 22 | BJ | | | | D05946J | 32 | | | 155-199 |
| 16A | 20 | | PA | 5-1 | 30-71-22 | D03968 | | C2 | | | | | TB0196X | A019 | BJ | | 050-099 |
| 16A | 20 | | PA | 5-1 | 30-71-22 | TB0196X | | A019 | BJ | | | | D03968 | C2 | | | 155-199 |
| 16A | 20 | | PA | 6-3 | 30-71-22 | D03968 | | C2 | | | | | TB0196X | A019 | BJ | | 276-299 |
| 170 | 20 | | PA | 5-0 | 30-71-21 | TB0188Y | | C002 | BJ | | | | D05946J | 1 | | | 150-199 |
| 171 | 20 | | PA | 4-8 | 30-71-21 | D05946J | | 40 | | | | | TB0186Y | A020 | BJ | | 050-099 |
| 171 | 20 | | PA | 4-7 | 30-71-21 | TB0186Z | | 23 | BJ | | | | D05946J | 40 | | | 150-199 |
| 173 | 20 | | PA | 5-0 | 30-71-21 | D05946J | | 4 | | | | | TB0188Y | A002 | BJ | | 050-099 |
| 175 | 22 | | PA | 0-7 | 30-31-21 | D01396 | | D3 | | | | | D01396 | D1 | | * | ALL |
| 176 | 22 | | PA | 0-7 | 30-31-21 | D01396 | | A2 | | | | | D01396 | D2 | | | ALL |
| 177 | 22 | | PA | 0-7 | 30-31-23 | D00624 | | D3 | | | * | | D00624 | D1 | | | ALL |
| 178 | 22 | | PA | 0-7 | 30-31-23 | D00624 | | D2 | | | | | D00624 | A2 | | | ALL |
| 179 | 24 | | PK | 5-3 | 73-21-16 | D05668J | | 38 | BJ | | | | D00630 | A2 | | | 050-099 |
| 179 | 24 | | PK | 6-3 | 73-21-16 | D05648J | | 21 | | | | | D00630 | A2 | | | 150-199 |
| 179 | 24 | | PK | 6-10 | 73-21-16 | D05668J | | 38 | | | | | TB0090Y | A004 | BJ | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 22
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | | |
| 17A | 22 | | PA | | 6-3 | 30-71-22 | D03968 | | D2 | | | | | TB0196X | B019 | BJ | | 276-299 |
| 180 | 24 | | PK | | 1-10 | 73-21-16 | TB0090Y | | A004 | BJ | | | | D00792 | B1 | | | 050-099, 150-199 |
| 180 | 24 | | PK | | 2-2 | 73-21-16 | TB0090Y | | A004 | BJ | | | | D00792 | D1 | | | 275-299 |
| 181 | 24 | | PK | | 6-5 | 73-21-16 | TB0090Y | | A004 | BJ | | | | D05668J | 9 | | | 050-099 |
| 181 | 24 | | PK | | 6-5 | 73-21-16 | D05668J | | | 9 | | | | TB0090Y | A004 | BJ | | 150-199 |
| 181 | 24 | | PK | | 6-10 | 73-21-16 | D05668J | | | 9 | | | | TB0090Y | A004 | BJ | | 275-299 |
| 185 | 22 | | PQ | HJ | 7-1 | 27-62-11 | D00630 | | | B3 | | | | TB0090G | 20 | | | ALL |
| 185Z | | | | HJ | 0-0 | 27-62-11 | D00630 | | | DED | | | | TB0090G | DED | | | ALL |
| 18A | 20 | | PA | | 2-1 | 22-32-13 | D11758 | | | 3 | | | | GDX0004 | D.. | 2 | | ALL |
| 18B | 24 | | PK | | 6-0 | 22-32-13 | D11758 | | | 7 | | | | TB0188X | B022 | BJ | | 050-099, 150-199 |
| 18B | 24 | | PK | | 6-9 | 22-32-13 | D11758 | | | 7 | | | | TB0188X | B022 | BJ | | 275-299 |
| 18C | 24 | | PV | PT | 6-2 | 73-21-14 | D11758 | | | 1 | | | | D05668J | 12 | | | ALL |
| 18CZ | | | | PT | 0-0 | 73-21-14 | D11758 | | | | | FH | | D05668J | 29 | | | ALL |
| 18D | 24 | | PV | ZZ | 5-1 | 73-21-14 | D11758 | | | 5 | | | | TB0200F | A007 | 2 | | 050-099, 150-199 |
| 18D | 24 | | PV | ZZ | 6-1 | 73-21-14 | D11758 | | | 5 | | | | TB0200F | A007 | 2 | | 275-299 |
| 18DZ | | | | ZZ | 0-0 | 73-21-14 | D11758 | | | | | FH | | TB0200F | C007 | 2 | | ALL |
| 18F | 24 | | PV | HR | 6-2 | 73-21-14 | D11758 | | | 6 | | | | D05668J | 31 | | | ALL |
| 18FZ | | | | HR | 0-0 | 73-21-14 | D11758 | | | | | FA | | D05668J | 32 | | | ALL |
| 18G | 24 | | PV | HS | 5-2 | 73-21-14 | D11758 | | | 2 | | | | TB0200Y | A005 | BJ | | 050-099, 150-199 |
| 18G | 24 | | PV | HS | 6-1 | 73-21-14 | D11758 | | | 2 | | | | TB0200Y | A005 | BJ | | 275-299 |
| 18GZ | | | | HS | 0-0 | 73-21-14 | D11758 | | | | | FB | | TB0200Y | C006 | BJ | | ALL |
| 18J | 24 | | PK | | 2-1 | 73-21-14 | D11758 | | | | | FH | | GDX0004 | S.. | 2 | | ALL |
| 19A | 24 | | PK | | 2-1 | 73-21-14 | D11758 | | | | | FA | | GDX0004 | S.. | 2 | | ALL |
| 19B | 24 | | PK | | 2-1 | 73-21-14 | D11758 | | | | | FB | | GDX0004 | S.. | 2 | | ALL |
| 19H | 22 | | PA | | 6-4 | 32-45-11 | D05668J | | | 30 | | | | TB0188Y | C003 | BJ | | 050-099, 150-199 |
| 19H | 22 | | PA | | 6-8 | 32-45-11 | D05668J | | | 30 | | | | TB0188Y | A008 | BJ | | 275-299 |
| 19L | 20 | | PA | | 4-7 | 30-71-21 | D05946J | | | 22 | | | | TB0186Z | 23 | BJ | | 050-099 |
| 19L | 20 | | PA | | 4-7 | 30-71-21 | TB0186Z | | | 23 | BJ | | | D05946J | 22 | | | 150-199 |
| 19M | 20 | | PA | | 4-7 | 30-71-21 | D05946J | | | 21 | | | | TB0186Z | 23 | BJ | | 050-099 |
| 19M | 20 | | PA | | 4-7 | 30-71-21 | TB0186Z | | | 23 | BJ | | | D05946J | 21 | | | 150-199 |
| 19N | 20 | | PA | | 4-7 | 30-71-21 | D05946J | | | 20 | | | | TB0186Z | 23 | BJ | | 050-099 |
| 19N | 20 | | PA | | 4-7 | 30-71-21 | TB0186Z | | | 23 | BJ | | | D05946J | 20 | | | 150-199 |
| 19P | 20 | | PA | | 4-7 | 30-71-21 | D05946J | | | 19 | | | | TB0186Z | 23 | BJ | | 050-099 |
| 19P | 20 | | PA | | 4-7 | 30-71-21 | TB0186Z | | | 23 | BJ | | | D05946J | 19 | | | 150-199 |
| 19R | 20 | | PA | | 4-7 | 30-71-21 | D05946J | | | 23 | | | | TB0186Z | 21 | BJ | | 150-199 |
| 19S | 20 | | PA | | 5-0 | 30-71-21 | TB0188Y | | | C004 | BJ | | | D05946J | 5 | | | 150-199 |
| 19T | 20 | | PA | | 4-7 | 30-71-21 | D05946J | | | 10 | | | | TB0186Z | 23 | BJ | | 050-099 |
| 19T | 20 | | PA | | 4-7 | 30-71-21 | TB0186Z | | | 23 | BJ | | | D05946J | 10 | | | 150-199 |
| 19U | 20 | | PA | | 2-8 | 30-71-23 | D05690J | | | 15 | | | | TB0188Z | 24 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 23

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|--------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | |
| 19U | 20 | | | PA | 2-8 | 30-71-23 | TB0188Z | | 24 | | BJ | | | | 150-199 |
| 201B | 24 | | | PL | 5-0 | 21-51-21 | D05744J | | 22 | | | | | | ALL |
| 201R | 24 | | | PL | 0-0 | 21-51-21 | D05744J | | 21 | | | | | | ALL |
| 202B | 24 | | | PL | 6-8 | 21-51-21 | D10130 | | 5 | | | | | | ALL |
| 202R | 24 | | | PL | 0-0 | 21-51-21 | D10130 | | 1 | | | | | | ALL |
| 203B | 22 | | | PB | 3-9 | 21-51-22 | D05744J | | 5 | | | D017 | BJ | | 050-099, 150-199 |
| 203B | 22 | | | PB | 4-5 | 21-51-22 | D05744J | | 5 | | | D017 | BJ | | 275-299 |
| 203R | 22 | | | PB | 0-0 | 21-51-22 | D05744J | | 4 | | | C017 | BJ | | ALL |
| 204B | 22 | | | PB | 3-9 | 21-51-22 | D05744J | | 6 | | | B018 | BJ | | 050-099, 150-199 |
| 204B | 22 | | | PB | 4-5 | 21-51-22 | D05744J | | 6 | | | B018 | BJ | | 275-299 |
| 204R | 22 | | | PB | 0-0 | 21-51-22 | D05744J | | 7 | | | A018 | BJ | | ALL |
| 20B | 20 | | | PA | 5-2 | 30-71-21 | TB0196X | | D019 | | BJ | C003 | BJ | | 050-099, 155-199 |
| 21A | 22 | | | PA | 7-0 | 23-34-11 | D02845 | | X1 | | | X1 | C | | 280-299 |
| 22A | 22 | | | PA | 7-0 | 23-34-11 | D02845 | | X2 | | | X2 | C | | 280-299 |
| 23A | 12 | | | PA | 12-8 | 23-34-17 | TB5096 | | 7 | | E | A2 | | | 280-299 |
| 24A | 12 | | | PA | 9-10 | 23-34-17 | D02845 | | A1 | | | 14 | | | 280-299 |
| 26R | 22 | | | PA | 4-8 | 27-62-11 | TB0196Z | | 5 | | BJ | X1 | | | ALL |
| 26S | 22 | | | PA | 7-6 | 27-62-11 | D05650J | | 16 | | | 5 | BJ | | ALL |
| 26T | 22 | | | PA | 7-6 | 27-62-11 | D05650J | | 15 | | | X2 | | | ALL |
| 26U | 22 | | | PA | 1-0 | 27-62-11 | D05650J | | 23 | | | | 9 | | ALL |
| 26W | 22 | | | PA | 1-0 | 27-62-11 | D05650J | | 24 | | | | 9 | | ALL |
| 26X | 20 | | | PA | 7-1 | 27-62-11 | SM00100 | | | | 9 | GD0001 | D.. | 2 | ALL |
| 35A | 24 | | | PK | 5-5 | 77-35-11 | TB0188X | | D019 | | BJ | 11 | | | 050-099 |
| 35A | 24 | | | PK | 5-5 | 77-35-11 | D05668J | | 11 | | | | D019 | BJ | 150-199 |
| 35A | 24 | | | PK | 6-8 | 77-35-11 | D05668J | | 11 | | | | D019 | BJ | 275-299 |
| 40A | 22 | | | PA | 11-2 | 30-81-11 | TB0266D | | A002 | 2 | | A009 | BJ | | 050-099, 150-199 |
| 40B | 22 | | | PA | 11-3 | 30-81-11 | TB0266D | | A006 | 2 | | A009 | BJ | | 050-099 |
| 40B | 22 | | | PA | 11-3 | 30-81-11 | TB0268Y | | A009 | BJ | | A006 | 2 | | 150-199 |
| 40C | 22 | | | PA | 0-7 | 30-81-11 | TB0266D | | C006 | 2 | | C005 | 2 | | 050-099, 150-199 |
| 40D | 22 | | | PA | 7-1 | 30-81-11 | D05648J | | 13 | | | C005 | 2 | | 050-099, 150-199 |
| 40E | 22 | | | PA | 7-0 | 30-81-11 | D05648J | | 15 | | | C004 | 2 | | 050-099, 150-199 |
| 40F | 22 | | | PA | 2-0 | 30-81-11 | D05648J | | 17 | | | 3 | | | 050-099, 150-199 |
| 40J | 22 | | | PA | 11-4 | 30-81-11 | TB0266D | | A008 | 2 | | A008 | BJ | | 050-099, 150-199 |
| 40K | 22 | | | PA | 1-1 | 30-81-11 | TB0266D | | A008 | 2 | | A005 | 2 | | 050-099, 150-199 |
| 40L | 22 | | | PA | 1-2 | 30-81-11 | TB0266D | | A007 | 2 | | A004 | 2 | | 050-099, 150-199 |
| 40M | 22 | | | PA | 1-2 | 30-81-11 | TB0266D | | A007 | 2 | | 11 | BJ | | 050-099, 150-199 |
| 40N | 20 | | | PA | 11-4 | 30-81-11 | TB0266D | | A003 | 2 | | 4 | BJ | | 050-099, 150-199 |
| 40P | 20 | | | PA | 2-5 | 30-81-11 | D00660 | | A2 | | | D.. | 2 | | 050-099, 150-199 |
| 40R | 22 | | | PA | 2-10 | 30-81-11 | D00660 | | A3 | | | B010 | BJ | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11
Section W0140
Page 24
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | |
| 40S | 22 | | PA | | 2-10 | 30-81-11 | D00660 | | A1 | | TB0266X | A010 | BJ | | 050-099, 150-199 |
| 40T | 22 | | PA | | 1-5 | 30-81-11 | TB0266D | | C003 | 2 | TB0266Y | C016 | BJ | | 050-099, 150-199 |
| 40U | 22 | | PA | | 7-3 | 30-81-11 | D05648J | | | 16 | TB0090Y | C014 | BJ | | 050-099, 150-199 |
| 40V | 22 | | PA | | 11-5 | 30-81-11 | D05648J | | | 25 | TB0092Y | A007 | BJ | | 050-099, 150-199 |
| 41B | 22 | | PA | | 11-4 | 30-81-11 | D12142 | | | 6 | TB0268Y | A008 | BJ | | 050-099, 150-199 |
| 41C | 22 | | PA | | 11-4 | 30-81-11 | D12142 | | | 2 | TB0268Y | A008 | BJ | | 050-099, 150-199 |
| 41D | 22 | | PA | | 3-1 | 30-81-11 | D12142 | | | 7 | TB0266Y | A015 | BJ | | 050-099, 150-199 |
| 41E | 22 | | PA | | 11-6 | 30-81-11 | D12142 | | | 3 | TB0268Z | | 4 | BJ | 050-099, 150-199 |
| 41F | 22 | | PA | | 3-0 | 30-81-11 | D12146 | | | 6 | TB0266Z | | 11 | BJ | 050-099, 150-199 |
| 41G | 22 | | PA | | 3-0 | 30-81-11 | D12146 | | | 2 | TB0266Z | | 11 | BJ | 050-099, 150-199 |
| 41H | 22 | | PA | | 7-3 | 30-81-11 | D12146 | | | 7 | D05648J | | 20 | | 050-099, 150-199 |
| 41J | 22 | | PA | | 11-7 | 30-81-11 | D12146 | | | 3 | TB0268Z | | 4 | BJ | 050-099, 150-199 |
| 41K | 22 | | PA | | 3-1 | 30-81-11 | D12150 | | | 4 | TB0266X | D010 | BJ | | 050-099, 150-199 |
| 41L | 22 | | PA | | 3-1 | 30-81-11 | D12150 | | | 5 | TB0266X | C010 | BJ | | 050-099, 150-199 |
| 41M | 22 | | PA | | 4-7 | 30-81-11 | D12142 | | | 1 | D05334J | | 20 | | 050-099, 150-199 |
| 41N | 22 | | PA | | 11-4 | 30-81-11 | D12142 | | | 5 | TB0268D | C010 | 2 | | 050-099, 150-199 |
| 41P | 22 | | PA | | 11-5 | 30-81-11 | D12146 | | | 1 | TB0092Y | A009 | BJ | | 050-099, 150-199 |
| 41R | 22 | | PA | | 11-4 | 30-81-11 | D12146 | | | 5 | TB0268D | C012 | 2 | | 050-099, 150-199 |
| 41S | 22 | | PA | | 7-4 | 30-81-11 | D12150 | | | 2 | D05648J | | 22 | | 050-099, 150-199 |
| 41T | 22 | | PA | | 3-2 | 30-81-11 | D12150 | | | 7 | TB0090Y | C014 | BJ | | 050-099, 150-199 |
| 41U | 22 | | PA | | 3-3 | 30-81-11 | D12150 | | | 3 | TB0266Y | C016 | BJ | | 050-099, 150-199 |
| 41V | 22 | | PA | | 4-8 | 30-81-11 | D05334J | | | 21 | TB0090Y | C014 | BJ | | 050-099 |
| 41V | 22 | | PA | | 4-8 | 30-81-11 | TB0090Y | | C014 | BJ | D05334J | | 21 | | 150-199 |
| 41W | 22 | | PA | | 2-2 | 30-81-11 | TB0268D | | A010 | 2 | TB0092Y | A007 | BJ | | 050-099, 150-199 |
| 41X | 22 | | PA | | 2-2 | 30-81-11 | TB0268D | | A012 | 2 | TB0092Y | A007 | BJ | | 050-099, 150-199 |
| 42A | 22 | | PA | | 1-0 | 30-11-11 | TB0268Z | | | 4 | TB0268Y | A006 | BJ | | 050-099 |
| 42A | 22 | | PA | | 1-0 | 30-11-11 | TB0268Y | | A006 | BJ | TB0268Z | | 4 | BJ | 150-199 |
| 42B | 22 | | PA | | 7-4 | 30-11-11 | D05648J | | | 32 | D12154 | | 8 | | 050-099, 150-199 |
| 42C | 22 | | PA | | 7-4 | 30-11-11 | D12154 | | | 1 | D05648J | | 34 | | 050-099 |
| 42C | 22 | | PA | | 7-4 | 30-11-11 | D05648J | | | 34 | D12154 | | 1 | | 150-199 |
| 42D | 22 | | PA | | 11-8 | 30-11-11 | D12154 | | | 6 | TB0268Z | | 4 | BJ | 050-099, 150-199 |
| 42E | 20 | | PA | | 2-9 | 30-11-11 | D12154 | | | 2 | GD0003 | | D.. | 2 | 050-099, 150-199 |
| 42F | 22 | | PA | | 11-8 | 30-11-11 | D12154 | | | 3 | TB0268Z | | 4 | BJ | 050-099, 150-199 |
| 42G | 22 | | PA | | 11-6 | 30-11-11 | D12154 | | | 7 | TB0268Y | A009 | BJ | | 050-099, 150-199 |
| 42H | 22 | | PA | | 11-5 | 30-11-11 | D05648J | | | 35 | TB0268Y | C008 | BJ | | 050-099, 150-199 |
| 42J | 22 | | PA | | 7-4 | 30-11-11 | D12154 | | | 5 | D05648J | | 36 | | 050-099, 150-199 |
| 42K | 22 | | PA | | 11-3 | 30-11-11 | D12152 | | | 7 | TB0268Z | | 4 | BJ | 050-099, 150-199 |
| 42L | 22 | | PA | | 11-2 | 30-11-11 | D12152 | | | 3 | TB0268Y | C008 | BJ | | 050-099 |
| 42L | 22 | | PA | | 11-2 | 30-11-11 | TB0268Y | | C008 | BJ | D12152 | | 3 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 25

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | | |
| 42M | 22 | | PA | | 11-2 | 30-11-11 | D12152 | | | 2 | | | | TB0268Y | C008 | BJ | | 050-099, 150-199 |
| 42N | 22 | | PA | | 11-2 | 30-11-11 | TB0268Y | | A009 | BJ | | | | TB0266D | A001 | 2 | | 050-099, 150-199 |
| 42P | 22 | | PA | | 2-6 | 30-11-11 | D12152 | | | 4 | | | | D00660 | C1 | | | 050-099, 150-199 |
| 42R | 20 | | PA | | 7-4 | 30-21-11 | D05648J | | | 8 | | | | TB0266D | A014 | 2 | | 050-099, 150-199 |
| 42S | 24 | | PK | | 6-5 | 21-51-11 | D00792 | | | C1 | | | | D05648J | 1 | | | 050-099, 150-199 |
| 42T | 20 | | PA | | 1-11 | 21-51-11 | D00792 | | | C2 | | | | GD0001 | D.. | 2 | | 050-099, 150-199 |
| 42U | 22 | | PA | | 6-3 | 30-11-11 | D05840J | | | 2 | | | | TB0090D | C018 | 2 | | 050-099, 150-199 |
| 42V | 22 | | PA | | 6-1 | 30-11-11 | D05650J | | | 8 | | | | TB0188D | C025 | 2 | | 050-099, 150-199 |
| 42W | 22 | | PA | | 6-7 | 30-81-11 | TB0266Y | | A015 | BJ | | | | TB0188D | A025 | 2 | | 050-099, 150-199 |
| 42X | 22 | | PA | | 1-2 | 30-81-11 | TB0266Y | | A015 | BJ | | | | TB0090D | A018 | 2 | | 050-099, 150-199 |
| 43R | 20 | | PA | | 1-4 | 30-21-11 | TB0266D | | C014 | 2 | | | | TB0266D | C004 | 2 | | 050-099, 150-199 |
| 50C | 24 | | PK | | 2-9 | 73-21-16 | TB0090Y | | A004 | BJ | | | | D00630 | A1 | | | 050-099, 150-199 |
| 50D | 22 | | PQ | NO | 8-4 | 30-34-11 | D10184 | | | D1 | | | | TB0186Y | C009 | BJ | | ALL |
| 50DZ | | | | NO | 0-0 | 30-34-11 | D10184 | | | DED | | | | TB0186Y | DED | | | ALL |
| 50E | 22 | | PA | | 1-2 | 30-81-11 | TB0266R | | | C018 | 2 | | | TB0266Y | A019 | BJ | | 050-099, 150-199 |
| 50F | 22 | | PA | | 1-2 | 30-81-11 | TB0266R | | | C017 | 2 | | | TB0266Y | A019 | BJ | | 050-099, 150-199 |
| 50G | 22 | | PA | | 11-10 | 30-81-11 | TB0266Y | | | A019 | BJ | | | TB0268Z | 4 | BJ | | 050-099, 150-199 |
| 50H | 22 | | PA | | 1-5 | 30-81-11 | TB0266D | | | C006 | 2 | | | TB0266R | A018 | 2 | | 050-099, 150-199 |
| 50L | 22 | | PQ | NP | 8-4 | 30-34-11 | D10184 | | | D2 | | | | TB0186Y | A010 | BJ | | ALL |
| 50LZ | | | | NP | 0-0 | 30-34-11 | D10184 | | | DED | | | | TB0186Y | DED | | | ALL |
| 542 | 20 | | PA | | 1-1 | 30-71-22 | TB0186Y | | A003 | BJ | | | | TB0188Y | C001 | BJ | | 050-099 |
| 542 | 22 | | PA | | 1-1 | 30-71-22 | TB0188Y | | | C001 | BJ | | | TB0186Y | A003 | BJ | | 150-199 |
| 542 | 22 | | PA | | 7-0 | 30-71-22 | TB0188Y | | | C001 | BJ | | | D03968 | D1 | | | 275-299 |
| 578 | 22 | | PA | | 2-11 | 30-34-21 | D00628 | | | D3 | | | | TB0090Y | A005 | BJ | | 050-099, 150-199 |
| 578 | 22 | | PA | | 3-3 | 30-34-21 | D00628 | | | D3 | | | | TB0090Y | A005 | BJ | | 275-299 |
| 579 | 24 | | PK | | 6-1 | 30-34-21 | D05668J | | | 5 | | | | D10232 | X2 | | | ALL |
| 581 | 22 | | PA | | 6-2 | 30-11-11 | D00660 | | | C3 | | | | D05648J | 23 | | | ALL |
| 582 | 22 | | PA | | 6-2 | 30-11-11 | D00660 | | | B2 | | | | D05648J | 24 | | | 050-099, 150-199 |
| 582 | 22 | | PA | | 6-2 | 30-11-11 | D00660 | | | C1 | | | | D05648J | 24 | | | 275-299 |
| 583 | 22 | | PA | | 6-11 | 30-11-11 | TB0090Y | | A011 | BJ | | | | D05650J | 13 | | | 050-099, 150-199 |
| 583 | 22 | | PA | | 5-4 | 30-11-11 | D00660 | | | A3 | | | | D05650J | 13 | | | 275-299 |
| 584 | 22 | | PA | | 4-6 | 30-11-11 | D00660 | | | B3 | | | | D05840J | 6 | | | 275-299 |
| 585 | 22 | | PA | | 3-0 | 30-11-11 | D00660 | | | B2 | | | | TB0090Y | A011 | BJ | | 275-299 |
| 586 | 22 | | PA | | 11-5 | 30-11-11 | TB0268Y | | A006 | BJ | | | | D05648J | 14 | | | 050-099, 150-199 |
| 586 | 22 | | PA | | 11-9 | 30-11-11 | TB0268Y | | A006 | BJ | | | | D05648J | 14 | | | 275-299 |
| 587 | 22 | | PA | | 5-5 | 30-11-11 | TB0186Y | | | C013 | BJ | | | D05908J | 16 | | | 050-099, 150-154, 156-199 |
| 587 | 22 | | PA | | 5-5 | 30-11-11 | TB0186Y | | | C013 | BJ | | | D05908J | 17 | | | 155 |
| 587 | 22 | | PA | | 7-2 | 30-11-11 | TB0186Y | | | C013 | BJ | | | D05648J | 18 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 26

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | |
| 588 | 22 | | PA | 5-5 | 30-11-11 | TB0186Y | A014 | BJ | | D05908J | 17 | | | 050-099, 150-154, 156-199 | | |
| 588 | 22 | | PA | 5-5 | 30-11-11 | TB0186Y | A014 | BJ | | D05908J | 16 | | | 155 | | |
| 588 | 22 | | PA | 7-2 | 30-11-11 | TB0186Y | A014 | BJ | | D05648J | 19 | | | 275-299 | | |
| 589 | 22 | | PA | 5-4 | 30-11-11 | D00660 | | A1 | | D05650J | 5 | | | 275-299 | | |
| 591 | 20 | | PA | 1-6 | 30-11-11 | D00914 | | X2 | | D00660 | C2 | | | 050-099, 150-199 | | |
| 591 | 20 | | PA | 2-11 | 30-11-11 | D00914 | | X2 | | GDX0003 | D.. | 2 | | 275-299 | | |
| 592 | 22 | | PA | 3-0 | 30-11-11 | D00914 | | A1 | | TB0090Y | A001 | BJ | | 050-099, 150-199 | | |
| 592 | 22 | | PA | 3-6 | 30-11-11 | D00914 | | A1 | | TB0090Y | A001 | BJ | | 275-299 | | |
| 593 | 22 | | PA | 3-5 | 30-11-11 | D00914 | | B3 | | TB0090D | C018 | 2 | | 050-099, 150-199 | | |
| 593 | 22 | | PA | 5-0 | 30-11-11 | D00914 | | B3 | | D05840J | 2 | | | 275-299 | | |
| 594 | 22 | | PA | 5-0 | 30-11-11 | D00914 | | B1 | | D05840J | 1 | | | ALL | | |
| 595 | 22 | | PA | 5-4 | 30-11-11 | D00914 | | C3 | | TB0188D | C025 | 2 | | 050-099, 150-199 | | |
| 595 | 22 | | PA | 6-3 | 30-11-11 | D00914 | | C3 | | D05650J | 8 | | | 275-299 | | |
| 596 | 22 | | PA | 6-3 | 30-11-11 | D00914 | | C1 | | D05650J | 7 | | | ALL | | |
| 597 | 22 | | PA | 6-1 | 30-11-11 | D05840J | | 6 | | TB0090Y | A011 | BJ | | 050-099, 150-199 | | |
| 597 | 22 | | PA | 3-0 | 30-11-11 | D00660 | | A2 | | TB0090Y | A011 | BJ | | 275-299 | | |
| 598 | 20 | | PA | 1-7 | 73-21-16 | D00792 | | B2 | | GDX0003 | D.. | 2 | | 050-099, 150-199 | | |
| 598 | 20 | | PA | 1-7 | 73-21-16 | D00792 | | D2 | | GDX0003 | D.. | 2 | | 275-299 | | |
| 599 | 22 | | PA | 2-0 | 30-11-11 | D00792 | | A1 | | TB0090Y | A011 | BJ | | 050-099, 150-199 | | |
| 599 | 22 | | PA | 2-2 | 30-11-11 | D00792 | | A1 | | TB0090Y | A011 | BJ | | 275-299 | | |
| 600 | 22 | | PA | 10-11 | 30-11-11 | TB0268Y | | C006 | BJ | D00914 | D2 | | | 050-099, 150-199 | | |
| 600 | 22 | | PA | 11-2 | 30-11-11 | TB0268Y | | C006 | BJ | D00914 | D2 | | | 275-299 | | |
| 601 | 22 | | PA | 1-9 | 30-11-11 | D00792 | | A2 | | TB0090Y | A001 | BJ | | 050-099, 150-199 | | |
| 601 | 22 | | PA | 2-2 | 30-11-11 | D00792 | | A2 | | TB0090Y | A001 | BJ | | 275-299 | | |
| 602 | 20 | | PA | 1-9 | 30-11-11 | D00792 | | X2 | | GDX0002 | D.. | 2 | | ALL | | |
| 603 | 22 | | PA | 1-9 | 30-11-11 | D00792 | | X1 | | TB0090Y | A001 | BJ | | 050-099, 150-199 | | |
| 603 | 22 | | PA | 2-2 | 30-11-11 | D00792 | | X1 | | TB0090Y | A001 | BJ | | 275-299 | | |
| 604 | 22 | | PA | 10-11 | 30-11-11 | TB0268Y | | A006 | BJ | D00914 | A2 | | | 050-099, 150-199 | | |
| 604 | 22 | | PA | 11-2 | 30-11-11 | TB0268Y | | A006 | BJ | D00914 | A2 | | | 275-299 | | |
| 605 | 22 | | PA | 10-11 | 30-11-11 | D00914 | | X1 | | TB0268Y | A006 | BJ | | 050-099 | | |
| 605 | 22 | | PA | 10-11 | 30-11-11 | TB0268Y | | A006 | BJ | D00914 | X1 | | | 150-199 | | |
| 605 | 22 | | PA | 1-6 | 30-11-11 | D00660 | | C2 | | D00914 | X1 | | | 275-299 | | |
| 606 | 22 | | PA | 6-7 | 30-11-11 | D00914 | | D3 | | D05648J | 30 | | | 050-099, 150-199 | | |
| 606 | 22 | | PA | 11-9 | 30-11-11 | TB0268Y | | C006 | BJ | D05648J | 30 | | | 275-299 | | |
| 607 | 22 | | PA | 10-0 | 30-11-11 | D12002 | | A2 | | GDX0002 | D.. | 2 | | ALL | | |
| 608 | 22 | | PA | 4-7 | 30-11-11 | D12002 | | A3 | | TB0186Y | C013 | BJ | | 050-099 | | |
| 608 | 22 | | PA | 4-7 | 30-11-11 | TB0186Y | | C013 | BJ | D12002 | A3 | | | 150-199 | | |
| 608 | 22 | | PA | 5-2 | 30-11-11 | TB0186Y | | C013 | BJ | D12002 | A3 | | | 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 27

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | |
| 609 | 22 | PA | | 2-7 | 30-11-11 | D00660 | | B1 | | TB0266D | C001 | 2 | | 050-099, 150-199 | |
| 609 | 22 | PA | | 4-6 | 30-11-11 | D00660 | | B1 | | D05840J | 3 | | | 275-299 | |
| 610 | 24 | PK | | 3-2 | 30-11-11 | D05334J | | 13 | | D05650J | 6 | | | ALL | |
| 611 | 24 | PK | | 2-4 | 30-11-11 | D05334J | | 15 | | D05840J | 5 | | | ALL | |
| 626 | 22 | PA | | 5-5 | 30-33-11 | D00628 | | C2 | | TB0186Y | A013 | BJ | | 050-099, 150-199 | |
| 626 | 22 | PA | | 6-5 | 30-33-11 | D00628 | | C2 | | TB0186Y | A013 | BJ | | 275-299 | |
| 628 | 22 | PA | | 5-5 | 30-31-21 | D10190 | | A1 | | TB0186X | A015 | BJ | | 050-099, 150-199 | |
| 628 | 22 | PA | | 6-6 | 30-31-21 | D10190 | | A1 | | TB0186X | A015 | BJ | | 275-299 | |
| 629 | 24 | PK | | 1-10 | 30-31-21 | D10190 | | X1 | | TB0090Z | 7 | BJ | | 050-099, 150-199 | |
| 629 | 24 | PK | | 2-1 | 30-31-21 | D10190 | | X1 | | TB0090Z | 7 | BJ | | 275-299 | |
| 630 | 20 | PA | | 1-8 | 30-31-21 | D10190 | | A2 | | GDX0002 | A.. | 2 | | ALL | |
| 631 | 24 | PK | | 5-5 | 30-31-21 | D10190 | | X2 | | D05668J | 36 | | | ALL | |
| 632 | 24 | PK | | 6-7 | 30-31-21 | TB0090Z | | 7 | BJ | TB0186X | A016 | BJ | | 050-099, 150-199 | |
| 632 | 24 | PK | | 7-5 | 30-31-21 | TB0090Z | | 7 | BJ | TB0186X | A016 | BJ | | 275-299 | |
| 633 | 22 | PA | | 4-7 | 30-31-21 | D05960J | | 9 | | D01396 | A3 | | | ALL | |
| 634 | 20 | PA | | 2-11 | 30-31-21 | D03938 | | X2 | | GDX0002 | D.. | 2 | | ALL | |
| 635 | 24 | PV | S | 1-7 | 30-31-21 | D03938 | | D3 | | D01396 | B2 | | | ALL | |
| 635Z | | | S | 0-0 | 30-31-21 | D03938 | | DED | | D01396 | DED | | | ALL | |
| 636 | 22 | PQ | T | 5-5 | 30-31-21 | D03938 | | D2 | | TB0188Y | C011 | BJ | | 050-099, 150-199 | |
| 636 | 22 | PQ | T | 6-6 | 30-31-21 | D03938 | | D2 | | TB0188Y | C011 | BJ | | 275-299 | |
| 636Z | | | T | 0-0 | 30-31-21 | D03938 | | DED | | TB0188Y | DED | | | ALL | |
| 637 | 24 | PK | | 3-0 | 30-31-21 | D03938 | | X1 | | TB0090Z | 7 | BJ | | 050-099, 150-199 | |
| 637 | 24 | PK | | 3-4 | 30-31-21 | D03938 | | X1 | | TB0090Z | 7 | BJ | | 275-299 | |
| 638 | 24 | PK | | 6-4 | 30-31-21 | D05908J | | 20 | | TB0090Z | 7 | BJ | | 050-099, 150-199 | |
| 638 | 24 | PK | | 6-8 | 30-31-21 | D05908J | | 20 | | TB0090Z | 7 | BJ | | 275-299 | |
| 639 | 20 | PQ | U | 2-11 | 30-31-21 | D03938 | | B2 | | GDX0002 | D.. | 2 | | ALL | |
| 639Z | | | U | 0-0 | 30-31-21 | D03938 | | DED | | GDX0002 | DED | | | ALL | |
| 640 | 22 | PA | | 4-11 | 30-31-21 | D01396 | | A1 | | TB0186X | C015 | BJ | | 050-099, 150-199 | |
| 640 | 22 | PA | | 6-0 | 30-31-21 | D01396 | | A1 | | TB0186X | C015 | BJ | | 275-299 | |
| 641 | 22 | PA | | 4-5 | 30-31-21 | D03938 | | C1 | | D05744J | 10 | | | ALL | |
| 642 | 22 | PA | | 1-7 | 30-31-21 | D03938 | | B1 | | D01396 | D1 | | * | ALL | |
| 643 | 24 | PV | R | 4-11 | 30-31-21 | D01396 | | B3 | | TB0186X | D015 | BJ | | 050-099, 150-199 | |
| 643 | 24 | PV | R | 6-0 | 30-31-21 | D01396 | | B3 | | TB0186X | D015 | BJ | | 275-299 | |
| 643Z | | | R | 0-0 | 30-31-21 | D01396 | | DED | | TB0186X | DED | | | ALL | |
| 644 | 24 | PK | | 5-4 | 30-31-21 | D05908J | | 21 | | TB0186X | B015 | BJ | | 050-099, 150-199 | |
| 644 | 24 | PK | | 6-5 | 30-31-21 | D05908J | | 21 | | TB0186X | B015 | BJ | | 275-299 | |
| 645 | 24 | PK | | 2-11 | 30-31-23 | D03910 | | X1 | | TB0090Z | 7 | BJ | | 050-099, 150-199 | |
| 645 | 24 | PK | | 3-3 | 30-31-23 | D03910 | | X1 | | TB0090Z | 7 | BJ | | 275-299 | |
| 646 | 24 | PK | | 2-5 | 30-34-21 | D10232 | | X1 | | TB0090Z | 7 | BJ | | 050-099, 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 28

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | |
| 646 | 24 | | PK | | 2-8 | 30-34-21 | D10232 | | X1 | | TB0090Z | 7 | BJ | | 275-299 |
| 647 | 22 | | PA | | 4-4 | 30-31-23 | D05744J | | 16 | | D03910 | | C1 | | ALL |
| 648 | 22 | | PQ | V | 5-4 | 30-31-23 | D03910 | | D2 | | TB0188Y | A012 | BJ | | 050-099, 150-199 |
| 648 | 22 | | PQ | V | 6-5 | 30-31-23 | D03910 | | D2 | | TB0188Y | A012 | BJ | | 275-299 |
| 648Z | | | | V | 0-0 | 30-31-23 | D03910 | | DED | | TB0188Y | | DED | | ALL |
| 649 | 24 | | PV | W | 1-4 | 30-31-23 | D03910 | | D3 | | D00624 | | B2 | | ALL |
| 649Z | | | | W | 0-0 | 30-31-23 | D03910 | | DED | | D00624 | | DED | | ALL |
| 650 | 20 | | PA | | 2-8 | 30-31-23 | D03910 | | D1 | | GDX0003 | | S.. | 2 | ALL |
| 651 | 20 | | PQ | BC | 2-8 | 30-31-23 | D03910 | | B2 | | GDX0003 | | D.. | 2 | ALL |
| 651Z | | | | BC | 0-0 | 30-31-23 | D03910 | | DED | | GDX0003 | | DED | | ALL |
| 652 | 22 | | PA | | 6-8 | 30-31-13 | D05648J | | 48 | | TB0186Y | C014 | BJ | | 050-099, 150-199 |
| 652 | 22 | | PA | | 7-2 | 30-31-13 | D05648J | | 48 | | TB0186Y | C014 | BJ | | 275-299 |
| 653 | 24 | | PK | | 4-1 | 30-31-13 | D05334J | | 5 | | TB0186Y | C014 | BJ | | 050-099, 150-199 |
| 653 | 24 | | PK | | 4-7 | 30-31-13 | D05334J | | 5 | | TB0186Y | C014 | BJ | | 275-299 |
| 654 | 24 | | PK | | 4-10 | 30-31-13 | D10184 | | C2 | | TB0186X | B016 | BJ | | 050-099, 150-199 |
| 654 | 24 | | PK | | 5-5 | 30-31-13 | D10184 | | C2 | | TB0186X | B016 | BJ | | 275-299 |
| 655 | 24 | | PK | | 3-4 | 30-31-13 | D05334J | | 6 | | D10184 | | C3 | | ALL |
| 656 | 22 | | PA | | 7-3 | 30-34-21 | D05648J | | 44 | | TB0090Y | A013 | BJ | | 050-099, 150-199 |
| 656 | 22 | | PA | | 7-5 | 30-34-21 | D05648J | | 44 | | TB0090Y | A013 | BJ | | 275-299 |
| 657 | 24 | | PV | X | 4-3 | 30-31-23 | TB0196X | | C014 | BJ | D00624 | | B3 | | 050-099, 150-199 |
| 657 | 24 | | PV | X | 4-10 | 30-31-23 | TB0196X | | C014 | BJ | D00624 | | B3 | | 275-299 |
| 657Z | | | | X | 0-0 | 30-31-23 | TB0196X | | DED | | D00624 | | DED | | ALL |
| 658 | 20 | | PA | | 2-8 | 30-31-23 | D03910 | | X2 | | GDX0003 | | D.. | 2 | ALL |
| 659 | 22 | | PA | | 3-2 | 30-34-21 | D00628 | | D2 | | TB0090Y | A013 | BJ | | 050-099, 150-199 |
| 659 | 22 | | PA | | 3-3 | 30-34-21 | D00628 | | D2 | | TB0090Y | A013 | BJ | | 275-299 |
| 660 | 22 | | PA | | 2-5 | 30-34-21 | D03946 | | C1 | | TB0090Y | A005 | BJ | | 050-099, 150-199 |
| 660 | 22 | | PA | | 2-10 | 30-34-21 | D03946 | | C1 | | TB0090Y | A005 | BJ | | 275-299 |
| 661 | 20 | | PA | | 2-2 | 30-34-21 | D03946 | | X2 | | GDX0004 | | D.. | 2 | ALL |
| 662 | 24 | | PK | | 1-2 | 30-34-21 | TB0090Y | | C011 | BJ | TB0090Z | | 7 | BJ | 050-099, 150-199 |
| 662 | 24 | | PK | | 0-7 | 30-34-21 | TB0090Y | | C011 | BJ | TB0090Z | | 7 | BJ | 275-299 |
| 664 | 22 | | PA | | 1-4 | 30-31-23 | D03910 | | B1 | | D00624 | | D3 | | ALL |
| 665 | 22 | | PA | | 4-10 | 30-34-21 | D03946 | | B1 | | D05668J | | 23 | | ALL |
| 667 | 22 | | PA | | 4-6 | 30-31-23 | D00624 | | A1 | | TB0196X | C003 | BJ | | 050-099, 150-199 |
| 667 | 22 | | PA | | 4-10 | 30-31-23 | D00624 | | A1 | | TB0196X | C003 | BJ | | 275-299 |
| 668 | 22 | | PA | | 1-9 | 30-32-21 | D10190 | | C2 | | TB0090Y | C005 | BJ | | 050-099, 150-199 |
| 668 | 22 | | PA | | 2-1 | 30-32-21 | D10190 | | C2 | | TB0090Y | C005 | BJ | | 275-299 |
| 670 | 22 | | PA | | 4-11 | 30-31-23 | D10190 | | B1 | | TB0196X | D003 | BJ | | 050-099, 150-199 |
| 670 | 22 | | PA | | 5-4 | 30-31-23 | D10190 | | B1 | | TB0196X | D003 | BJ | | 275-299 |
| 671 | 22 | | PQ | AU | 5-0 | 30-31-13 | D00624 | | C1 | | TB0186X | D016 | BJ | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 29

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | |
| 671 | 22 | PQ | AU | 6-1 | 30-31-13 | D00624 | | C1 | | | TB0186X | D016 | BJ | | 275-299 | |
| 671Z | | | AU | 0-0 | 30-31-13 | D00624 | | DED | | | TB0186X | DED | | | ALL | |
| 672 | 22 | PQ | BD | 5-3 | 30-31-13 | D00624 | | C2 | | | TB0186X | D002 | BJ | | 050-099, 150-199 | |
| 672 | 22 | PQ | BD | 6-1 | 30-31-13 | D00624 | | C2 | | | TB0186X | D002 | BJ | | 275-299 | |
| 672Z | | | BD | 0-0 | 30-31-13 | D00624 | | DED | | | TB0186X | DED | | | ALL | |
| 684 | 20 | PA | | 4-4 | 24-31-11 | D04128J | | 1 | | | D00342 | A2 | | | ALL | |
| 685 | 20 | PA | | 4-4 | 24-31-11 | D04128J | | 2 | | | D00342 | B2 | | | ALL | |
| 686 | 20 | PA | | 4-4 | 24-31-11 | D04128J | | 3 | | | D00342 | C2 | | | ALL | |
| 687 | 20 | PA | | 4-5 | 30-71-21 | D03964 | | C1 | | | D05946J | 11 | | | 050-099, 150-199 | |
| 687 | 22 | PA | | 6-4 | 30-71-21 | D03964 | | C1 | | | TB0188Y | A004 | BJ | | 280-299 | |
| 688 | 20 | PA | | 8-9 | 30-71-21 | TB0090Y | | C003 | BJ | | C01155 | 1 | D | | 150-154 | |
| 691 | 14 | PA | | 4-9 | 27-51-11 | D05322J | | 3 | | | K00359 | C2 | E | | 050-099 | |
| 691 | 14 | PA | | 6-0 | 27-51-11 | D05322J | | 3 | | | K00359 | C2 | E | | 150-199, 275-299 | |
| 692 | 14 | PA | | 4-9 | 27-51-11 | D05322J | | 2 | | | K00359 | B2 | E | | ALL | |
| 693 | 14 | PA | | 4-8 | 27-51-11 | D05322J | | 1 | | | K00359 | A2 | E | | ALL | |
| 694 | 20 | PA | | 3-2 | 30-71-21 | D05690J | | 4 | | | TB0188Y | A002 | BJ | | 050-099 | |
| 694 | 22 | PA | | 3-6 | 30-71-22 | TB0188Y | | C003 | BJ | | D05690J | 4 | | | 275-299 | |
| 695 | 20 | PA | | 6-0 | 30-71-21 | TB0188Y | | A004 | BJ | | D03964 | B1 | | | 050-099 | |
| 695 | 22 | PA | | 6-0 | 30-71-21 | TB0188Y | | A004 | BJ | | D03964 | B1 | | | 150-154 | |
| 695 | 20 | PA | | 5-1 | 30-71-21 | TB0186Z | | 22 | BJ | | D03964 | B1 | | | 155-199 | |
| 695 | 22 | PA | | 6-4 | 30-71-21 | TB0188Y | | A004 | BJ | | D03964 | B1 | | | 275-278 | |
| 697 | 20 | PA | | 5-1 | 30-71-21 | TB0186Z | | 23 | BJ | | D03964 | D1 | | | 050-099, 150-199 | |
| 697 | 22 | PA | | 4-5 | 30-71-21 | D05946J | | 10 | | | D03964 | D1 | | | 275-299 | |
| 698 | 20 | PA | | 4-5 | 30-71-21 | D05946J | | 6 | | | D03964 | X2 | | | 050-099, 155-199 | |
| 698 | 22 | PA | | 4-5 | 30-71-21 | D05946J | | 6 | | | D03964 | X2 | | | 150-154, 275-299 | |
| 699 | 22 | PA | | 6-1 | 30-71-21 | D03966 | | A1 | | | D05690J | 35 | | | 280-299 | |
| 700 | 22 | PA | | 2-4 | 30-11-11 | D12002 | | X1 | | | TB0268Y | C006 | BJ | | 050-099 | |
| 700 | 22 | PA | | 2-4 | 30-11-11 | TB0268Y | | C006 | BJ | | D12002 | X1 | | | 150-199 | |
| 700 | 22 | PA | | 2-8 | 30-11-11 | TB0268Y | | C006 | BJ | | D12002 | X1 | | | 275-299 | |
| 701 | 22 | PA | | 6-9 | 30-71-21 | D03966 | | A1 | | | TB0188Y | A002 | BJ | | 050-099 | |
| 701 | 20 | PA | | 6-4 | 30-71-21 | D03966 | | A1 | | | TB0186Z | 21 | BJ | | 150-199 | |
| 701 | 22 | PA | | 7-1 | 30-71-21 | D03966 | | B1 | | | TB0188Y | C004 | BJ | | 275-299 | |
| 702 | 20 | PA | | 6-1 | 30-71-21 | D05690J | | 36 | | | D03966 | X2 | | | 150-199 | |
| 702 | 22 | PA | | 6-1 | 30-71-21 | D05690J | | 36 | | | D03966 | X2 | | | 275-299 | |
| 703 | 22 | PA | | 0-7 | 30-71-22 | TB0188Z | | 15 | BJ | | TB0188Y | C003 | BJ | | 275-299 | |
| 704 | 20 | PA | | 2-10 | 30-71-22 | D05690J | | 16 | | | TB0188Z | 15 | BJ | | 050-099, 155-199 | |
| 704 | 22 | PA | | 2-10 | 30-71-22 | D05690J | | 16 | | | TB0188Z | 15 | BJ | | 150-154 | |
| 705 | 20 | PA | | 2-10 | 30-71-21 | D05690J | | 5 | | | TB0186Y | C020 | BJ | | 050-099 | |
| 706 | 20 | PA | | 2-10 | 30-71-21 | D05690J | | 6 | | | TB0186Y | C020 | BJ | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 30

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|--------|-------------|------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | | | |
| 707 | 20 | | PA | | 3-0 | 30-71-21 | D05690J | | | | 7 | | | | TB0186Y | A012 | BJ | | 050-099, 155-199 |
| 707 | 22 | | PA | | 3-0 | 30-71-21 | D05690J | | | | 7 | | | | TB0186Y | A012 | BJ | | 150-154 |
| 707 | 22 | | PA | | 3-6 | 30-71-21 | D05690J | | | | 7 | | | | TB0186Y | A012 | BJ | | 275-299 |
| 708 | 20 | | PA | | 6-1 | 30-71-21 | D03966 | | | | X2 | | | | D05690J | | 8 | | 050-099 |
| 709 | 20 | | PA | | 2-8 | 30-71-23 | D05690J | | | | 9 | | | | TB0188Z | 23 | BJ | | 050-099, 150-199 |
| 709 | 22 | | PA | | 3-6 | 30-71-23 | D05690J | | | | 15 | | | | TB0188Z | 23 | BJ | | 275-299 |
| 70B | 20 | | PA | | 2-3 | 29-11-14 | D13188 | | | | 2 | | | | GDX0004 | D.. | 2 | | ALL |
| 70C | 20 | | PQ | AW | 5-3 | 29-11-14 | D13188 | | | | 7 | | | | TB0196Y | C008 | BJ | | 050-099, 150-199 |
| 70C | 20 | | PQ | AW | 6-3 | 29-11-14 | D13188 | | | | 7 | | | | TB0196Y | C008 | BJ | | 275-299 |
| 70CZ | | | | AW | 0-0 | 29-11-14 | D13188 | | | | DED | | | | TB0196Y | DED | | | ALL |
| 70D | 20 | | PQ | AI | 6-4 | 29-11-14 | D13188 | | | | 3 | | | | TB0186Y | A017 | BJ | | 050-099, 150-199 |
| 70D | 20 | | PQ | AI | 6-11 | 29-11-14 | D13188 | | | | 3 | | | | TB0186Y | A017 | BJ | | 275-299 |
| 70DZ | | | | AI | 0-0 | 29-11-14 | D13188 | | | | DED | | | | TB0186Y | DED | | | ALL |
| 70F | 20 | | PA | | 4-11 | 29-11-14 | D13188 | | | | 6 | | | | TB0200Y | C024 | BJ | | 050-099, 150-199 |
| 70F | 20 | | PA | | 6-3 | 29-11-14 | D13188 | | | | 6 | | | | TB0200Y | C024 | BJ | | 275-299 |
| 70G | 20 | | PQ | AY | 6-2 | 29-11-14 | D13188 | | | | 1 | | | | TB0188X | D022 | BJ | | 050-099, 150-199 |
| 70G | 20 | | PQ | AY | 6-11 | 29-11-14 | D13188 | | | | 1 | | | | TB0188X | D022 | BJ | | 275-299 |
| 70GZ | | | | AY | 0-0 | 29-11-14 | D13188 | | | | DED | | | | TB0188X | DED | | | ALL |
| 70K | 20 | | PA | | 5-1 | 29-11-14 | D04803J | | | | 15 | | | | TB0196X | C018 | BJ | | 050-099, 150-199 |
| 70K | 20 | | PA | | 6-4 | 29-11-14 | D04803J | | | | 15 | | | | TB0196X | C018 | BJ | | 275-299 |
| 70M | 20 | | PA | | 5-1 | 29-11-14 | D04803J | | | | 13 | | | | TB0196X | D018 | BJ | | 050-099, 150-199 |
| 70M | 20 | | PA | | 6-4 | 29-11-14 | D04803J | | | | 13 | | | | TB0196X | D018 | BJ | | 275-299 |
| 70T | 20 | | PQ | AX | 6-2 | 29-11-14 | D13188 | | | | 5 | | | | TB0188X | C022 | BJ | | 050-099, 150-199 |
| 70T | 20 | | PQ | AX | 6-11 | 29-11-14 | D13188 | | | | 5 | | | | TB0188X | C022 | BJ | | 275-299 |
| 70TZ | | | | AX | 0-0 | 29-11-14 | D13188 | | | | DED | | | | TB0188X | DED | | | ALL |
| 710 | 20 | | PA | | 4-10 | 30-71-23 | TB0188Z | | | | 24 | BJ | | | D03972 | C1 | | | 050-099, 150-199 |
| 710 | 22 | | PA | | 4-8 | 30-71-23 | D05690J | | | | 9 | | | | D03972 | C1 | | | 275-299 |
| 711 | 20 | | PA | | 6-3 | 30-71-23 | D05690J | | | | 11 | | | | TB0090Z | 9 | BJ | | 050-099, 155-199 |
| 711 | 22 | | PA | | 6-3 | 30-71-23 | D05690J | | | | 11 | | | | TB0090Z | 9 | BJ | | 150-154 |
| 711 | 22 | | PA | | 6-6 | 30-71-23 | D05690J | | | | 11 | | | | TB0090Z | 9 | BJ | | 275-299 |
| 712 | 20 | | PA | | 2-8 | 30-71-23 | D05690J | | | | 14 | | | | TB0188Z | 24 | BJ | | 050-099 |
| 712 | 22 | | PA | | 3-1 | 30-71-23 | D05690J | | | | 14 | | | | TB0186Y | A006 | BJ | | 150-154 |
| 712 | 20 | | PA | | 3-1 | 30-71-23 | D05690J | | | | 14 | | | | TB0186Y | A006 | BJ | | 155-199 |
| 712 | 22 | | PA | | 3-6 | 30-71-23 | D05690J | | | | 14 | | | | TB0186Y | A006 | BJ | | 275-299 |
| 713 | 22 | | PA | | 2-10 | 30-71-22 | D05690J | | | | 12 | | | | TB0188Z | 15 | BJ | | 150-154 |
| 713 | 20 | | PA | | 2-10 | 30-71-22 | D05690J | | | | 12 | | | | TB0188Z | 15 | BJ | | 155-199 |
| 715 | 20 | | PA | | 4-7 | 30-71-21 | D05946J | | | | 2 | | | | TB0186Z | 23 | BJ | | 050-099, 155-199 |
| 715 | 22 | | PA | | 4-7 | 30-71-21 | D05946J | | | | 2 | | | | TB0186Z | 23 | BJ | | 150-154 |
| 715 | 22 | | PA | | 5-4 | 30-71-21 | D05946J | | | | 2 | | | | TB0188Y | A002 | BJ | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 31

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | | | |
| 716 | 22 | PA | | | 6-3 | 30-71-23 | TB0090Z | | 9 | BJ | | | | D05690J | 10 | | | | 150-154 |
| 716 | 20 | PA | | | 6-3 | 30-71-23 | TB0090Z | | 9 | BJ | | | | D05690J | 10 | | | | 155-199 |
| 716 | 22 | PA | | | 6-6 | 30-71-23 | TB0090Z | | 9 | BJ | | | | D05690J | 10 | | | | 275-299 |
| 718 | 22 | PA | | | 5-0 | 30-71-22 | D05946J | | 27 | | | | | TB0186Y | A003 | BJ | | | 150-199 |
| 719 | 24 | PK | | | 6-4 | 24-31-11 | D00342 | | X1 | | | | | TB0186X | A001 | BJ | | | 050-099, 150-199 |
| 719 | 24 | PK | | | 6-7 | 24-31-11 | D00342 | | X1 | | | | | TB0186X | A001 | BJ | | | 275-299 |
| 71A | 20 | PA | | | 5-1 | 29-11-14 | D11964 | | 2 | | | | | TB0200Y | C024 | BJ | | | 050-099, 150-199 |
| 71A | 20 | PA | | | 6-4 | 29-11-14 | D11964 | | 2 | | | | | TB0200Y | C024 | BJ | | | 275-299 |
| 71B | 20 | PQ | AZ | | 5-1 | 29-11-14 | D11964 | | 1 | | | | | TB0200Y | A023 | BJ | | | 050-099, 150-199 |
| 71B | 20 | PQ | AZ | | 6-4 | 29-11-14 | D11964 | | 1 | | | | | TB0200Y | A023 | BJ | | | 275-299 |
| 71BZ | | | AZ | | 0-0 | 29-11-14 | D11964 | | DED | | | | | TB0200Y | DED | | | | ALL |
| 71C | 20 | PQ | AM | | 5-3 | 29-11-14 | D11964 | | 6 | | | | | TB0196F | A013 | 2 | | | 050-099, 150-199 |
| 71C | 20 | PQ | AM | | 6-4 | 29-11-14 | D11964 | | 6 | | | | | TB0196F | A013 | 2 | | | 275-299 |
| 71CZ | | | AM | | 0-0 | 29-11-14 | D11964 | | DED | | | | | TB0196F | DED | | | | ALL |
| 71D | 20 | PA | | | 2-4 | 29-11-14 | D11964 | | 12 | | | | | GD0004 | D.. | 2 | | | ALL |
| 71E | 20 | PA | | | 5-0 | 29-11-14 | D11962 | | 2 | | | | | TB0200Y | C024 | BJ | | | 050-099, 150-199 |
| 71E | 20 | PA | | | 6-3 | 29-11-14 | D11962 | | 2 | | | | | TB0200Y | C024 | BJ | | | 275-299 |
| 71F | 20 | PQ | AV | | 5-0 | 29-11-14 | D11962 | | 1 | | | | | TB0200Y | A023 | BJ | | | 050-099, 150-199 |
| 71F | 20 | PQ | AV | | 6-3 | 29-11-14 | D11962 | | 1 | | | | | TB0200Y | A023 | BJ | | | 275-299 |
| 71FZ | | | AV | | 0-0 | 29-11-14 | D11962 | | DED | | | | | TB0200Y | DED | | | | ALL |
| 71G | 20 | PA | | | 2-4 | 29-11-14 | D11962 | | 12 | | | | | GD0004 | D.. | 2 | | | ALL |
| 71H | 20 | PQ | AN | | 5-2 | 29-11-14 | D11962 | | 6 | | | | | TB0196F | C013 | 2 | | | 050-099, 150-199 |
| 71H | 20 | PQ | AN | | 6-3 | 29-11-14 | D11962 | | 6 | | | | | TB0196F | C013 | 2 | | | 275-299 |
| 71HZ | | | AN | | 0-0 | 29-11-14 | D11962 | | DED | | | | | TB0196F | DED | | | | ALL |
| 720 | 24 | PK | | | 6-4 | 24-31-11 | D00342 | | X2 | | | | | TB0186X | B001 | BJ | | | 050-099, 150-199 |
| 720 | 24 | PK | | | 6-7 | 24-31-11 | D00342 | | X2 | | | | | TB0186X | B001 | BJ | | | 275-299 |
| 721 | 20 | PA | | | 4-5 | 30-71-21 | D03964 | | A1 | | | | | D05946J | 1 | | | | 050-099 |
| 721 | 20 | PA | | | 6-0 | 30-71-21 | D03964 | | A1 | | | | | TB0188Y | C002 | BJ | | | 150-199 |
| 721 | 22 | PA | | | 6-4 | 30-71-21 | D03964 | | A1 | | | | | TB0188Y | A002 | BJ | | | 275-299 |
| 722 | 20 | PA | | | 3-1 | 30-71-21 | D03964 | | A2 | | | | | TB0090H | 16 | 2 | | | 050-099, 155-199 |
| 722 | 22 | PA | | | 3-1 | 30-71-21 | D03964 | | A2 | | | | | TB0090H | 16 | 2 | | | 150-154 |
| 722 | 22 | PA | | | 3-2 | 30-71-21 | D03964 | | A2 | | | | | TB0090H | 16 | 2 | | | 275-299 |
| 723 | 20 | PA | | | 3-1 | 30-71-21 | D03964 | | B2 | | | | | TB0090H | 16 | 2 | | | 050-099, 155-199 |
| 723 | 22 | PA | | | 3-1 | 30-71-21 | D03964 | | B2 | | | | | TB0090H | 16 | 2 | | | 150-154 |
| 723 | 22 | PA | | | 3-2 | 30-71-21 | D03964 | | B2 | | | | | TB0090H | 16 | 2 | | | 275-278 |
| 724 | 20 | PA | | | 3-1 | 30-71-21 | D03964 | | C2 | | | | | TB0090H | 16 | 2 | | | 050-099 |
| 724 | 20 | PA | | | 3-1 | 30-71-21 | TB0090H | | 16 | 2 | | | | D03964 | C2 | | | | 150-199 |
| 724 | 22 | PA | | | 3-2 | 30-71-21 | TB0090H | | 16 | 2 | | | | D03964 | C2 | | | | 280-299 |
| 725 | 20 | PA | | | 3-1 | 30-71-21 | D03964 | | D2 | | | | | TB0090H | 16 | 2 | | | 050-099, 155-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 32

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 725 | 22 | | PA | 3-1 | 30-71-21 | D03964 | | D2 | | | | | TB0090H | 16 | 2 | | 150-154 |
| 725 | 22 | | PA | 3-2 | 30-71-21 | D03964 | | D2 | | | | | TB0090H | 16 | 2 | | 275-299 |
| 726 | 20 | | PA | 3-1 | 30-71-21 | D03964 | | X1 | | | | | TB0090H | 16 | 2 | | 050-099, 155-199 |
| 726 | 22 | | PA | 3-1 | 30-71-21 | D03964 | | X1 | | | | | TB0090H | 16 | 2 | | 150-154 |
| 726 | 22 | | PA | 3-2 | 30-71-21 | D03964 | | X1 | | | | | TB0090H | 16 | 2 | | 275-299 |
| 727 | 20 | | PA | 2-2 | 30-71-21 | D03966 | | A2 | | | | | TB0090Y | C003 | BJ | | 050-099 |
| 727 | 20 | | PA | 2-2 | 30-71-21 | TB0090Y | | C003 | BJ | | | | D03966 | A2 | | | 150-199 |
| 727 | 22 | | PA | 2-7 | 30-71-21 | D03966 | | A2 | | | | | TB0090H | 16 | 2 | | 280-299 |
| 728 | 20 | | PA | 2-2 | 30-71-21 | D03966 | | B2 | | | | | TB0090Y | C003 | BJ | | 050-099, 150-199 |
| 728 | 22 | | PA | 2-7 | 30-71-21 | D03966 | | B2 | | | | | TB0090H | 16 | 2 | | 275-299 |
| 729 | 20 | | PA | 6-5 | 30-71-22 | D03968 | | A1 | | | | | TB0188Z | 15 | BJ | | 050-099, 155-199 |
| 729 | 22 | | PA | 6-5 | 30-71-22 | D03968 | | A1 | | | | | TB0188Z | 15 | BJ | | 150-154 |
| 729 | 22 | | PA | 7-0 | 30-71-22 | D03968 | | A1 | | | | | TB0188Z | 15 | BJ | | 275-299 |
| 730 | 20 | | PA | 3-2 | 30-71-22 | D05690J | | 2 | | | | | TB0186Y | A003 | BJ | | 050-099 |
| 730 | 22 | | PA | 3-2 | 30-71-22 | D05690J | | 2 | | | | | TB0186Y | A003 | BJ | | 150-199 |
| 730 | 22 | | PA | 3-6 | 30-71-22 | D05690J | | 2 | | | | | TB0186Y | A003 | BJ | | 275-299 |
| 731 | 20 | | PA | 6-5 | 30-71-22 | D03968 | | B1 | | | | | TB0188Z | 16 | BJ | | 050-099 |
| 731 | 22 | | PA | 6-5 | 30-71-22 | D03968 | | B1 | | | | | TB0188Z | 16 | BJ | | 150-199 |
| 731 | 22 | | PA | 7-0 | 30-71-22 | D03968 | | B1 | | | | | TB0188Z | 16 | BJ | | 275-299 |
| 732 | 20 | | PA | 5-1 | 30-71-22 | D03968 | | B2 | | | | | TB0196X | B019 | BJ | | 050-099 |
| 732 | 22 | | PA | 8-8 | 30-71-22 | D03968 | | B2 | | | | | C01157 | 1 | D | | 150-154 |
| 732 | 22 | | PA | 5-1 | 30-71-22 | D03968 | | B2 | | | | | TB0196X | B019 | BJ | | 155-199 |
| 732 | 22 | | PA | 6-1 | 30-71-22 | D03968 | | B2 | | | | | D05960J | 8 | | | 275 |
| 732 | 22 | | PA | 6-3 | 30-71-22 | D03968 | | B2 | | | | | TB0196X | C019 | BJ | | 276-299 |
| 733 | 20 | | PA | 6-7 | 30-71-22 | D03968 | | X1 | | | | | TB0186Y | C010 | BJ | | 050-099, 155-199 |
| 733 | 22 | | PA | 2-1 | 30-71-22 | D03968 | | X1 | | | | | TB0090Y | A003 | BJ | | 150-154 |
| 733 | 22 | | PA | 2-6 | 30-71-22 | D03968 | | X1 | | | | | TB0090Y | A003 | BJ | | 275 |
| 733 | 22 | | PA | 7-0 | 30-71-22 | D03968 | | X1 | | | | | TB0186Y | C010 | BJ | | 276-299 |
| 734 | 20 | | PA | 6-1 | 30-71-22 | D03968 | | X2 | | | | | D05690J | 3 | | | 050-099, 155-199 |
| 734 | 22 | | PA | 6-1 | 30-71-22 | D03968 | | X2 | | | | | D05690J | 3 | | | 150-154 |
| 734 | 22 | | PA | 6-0 | 30-71-22 | D03968 | | X2 | | | | | D05690J | 3 | | | 275-299 |
| 735 | 20 | | PA | 4-10 | 30-71-23 | D03972 | | A1 | | | | | TB0188Z | 23 | BJ | | 050-099, 155-199 |
| 735 | 22 | | PA | 4-10 | 30-71-23 | D03972 | | A1 | | | | | TB0188Z | 23 | BJ | | 150-154 |
| 735 | 22 | | PA | 6-2 | 30-71-23 | D03972 | | A1 | | | | | TB0188Z | 23 | BJ | | 275-299 |
| 736 | 20 | | PA | 5-4 | 30-71-23 | D03972 | | A2 | | | | | TB0186Y | C004 | BJ | | 050-099, 150-199 |
| 736 | 22 | | PA | 4-9 | 30-71-23 | D03972 | | A2 | | | | | D05960J | 3 | | | 275 |
| 736 | 22 | | PA | 6-2 | 30-71-23 | D03972 | | A2 | | | | | TB0186X | D001 | BJ | | 276-299 |
| 737 | 22 | | PA | 5-3 | 30-71-23 | D03972 | | B1 | | | | | TB0186Y | A006 | BJ | | 150-154 |
| 737 | 20 | | PA | 5-3 | 30-71-23 | D03972 | | B1 | | | | | TB0186Y | A006 | BJ | | 155-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 33

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | |
| 737 | 22 | | PA | 6-2 | 30-71-23 | D03972 | | B1 | | | | TB0186Y | A006 | BJ | | 275-299 |
| 738 | 20 | | PA | 5-4 | 30-71-23 | D03972 | | B2 | | | | TB0186Y | C004 | BJ | | 050-099, 150-199 |
| 738 | 22 | | PA | 6-2 | 30-71-23 | D03972 | | B2 | | | | TB0186Y | C006 | BJ | | 275-299 |
| 739 | 20 | | PA | 5-3 | 30-71-23 | D03972 | | C2 | | | | TB0186Z | 7 | BJ | | 050-099, 155-199 |
| 739 | 22 | | PA | 5-3 | 30-71-23 | D03972 | | C2 | | | | TB0186Z | 7 | BJ | | 150-154 |
| 739 | 22 | | PA | 6-2 | 30-71-23 | D03972 | | C2 | | | | TB0186Z | 7 | BJ | | 275-299 |
| 740 | 20 | | PA | 2-9 | 30-71-23 | D03972 | | D1 | | | | TB0090Z | 9 | BJ | | 050-099, 155-199 |
| 740 | 22 | | PA | 2-9 | 30-71-23 | D03972 | | D1 | | | | TB0090Z | 9 | BJ | | 150-154 |
| 740 | 22 | | PA | 3-0 | 30-71-23 | D03972 | | D1 | | | | TB0090Z | 9 | BJ | | 275-299 |
| 741 | 20 | | PA | 5-3 | 30-71-23 | D03972 | | D2 | | | | TB0186Z | 7 | BJ | | 050-099, 155-199 |
| 741 | 22 | | PA | 5-3 | 30-71-23 | D03972 | | D2 | | | | TB0186Z | 7 | BJ | | 150-154 |
| 741 | 22 | | PA | 6-2 | 30-71-23 | D03972 | | D2 | | | | TB0186Z | 7 | BJ | | 275-299 |
| 742 | 20 | | PA | 5-3 | 30-71-23 | D03972 | | X1 | | | | TB0186Z | 7 | BJ | | 050-099, 155-199 |
| 742 | 22 | | PA | 5-3 | 30-71-23 | D03972 | | X1 | | | | TB0186Z | 7 | BJ | | 150-154 |
| 742 | 22 | | PA | 6-2 | 30-71-23 | D03972 | | X1 | | | | TB0186Z | 7 | BJ | | 275-299 |
| 743 | 20 | | PA | 2-10 | 30-71-22 | D05690J | | 19 | | | | TB0188Z | 15 | BJ | | 050-099, 155-199 |
| 743 | 22 | | PA | 2-10 | 30-71-22 | D05690J | | 19 | | | | TB0188Z | 15 | BJ | | 150-154 |
| 743 | 22 | | PA | 3-6 | 30-71-22 | D05690J | | 19 | | | | TB0186Y | A003 | BJ | | 275-299 |
| 745 | 14 | | PA | 1-9 | 27-51-11 | K00359 | | A1 | E | | | K00360 | A1 | E | | ALL |
| 746 | 14 | | PA | 1-11 | 27-51-11 | K00359 | | C2 | E | | | K00360 | C2 | E | | 050-099 |
| 746 | 14 | | PA | 3-0 | 27-51-11 | K00359 | | C2 | E | | | K00360 | C2 | E | | 150-199, 275-299 |
| 748 | 14 | | PA | 1-10 | 27-51-11 | K00359 | | B1 | E | | | K00360 | B1 | E | | ALL |
| 749 | 14 | | PA | 1-9 | 27-51-11 | K00359 | | B2 | E | | | K00360 | A2 | E | | ALL |
| 750 | 14 | | PA | 1-11 | 27-51-11 | K00359 | | C1 | E | | | K00360 | C1 | E | | ALL |
| 751 | 14 | | PA | 1-9 | 27-51-11 | K00359 | | A2 | E | | | K00360 | B2 | E | | ALL |
| 752 | 22 | | PA | 1-8 | 27-51-11 | K00359 | | X2 | C | | | K00360 | 13 | C | | 050-099 |
| 752 | 22 | | PA | 3-0 | 27-51-11 | K00359 | | X2 | C | | | K00360 | 13 | C | | 150-199, 275-299 |
| 753 | 22 | | PA | 1-8 | 27-51-11 | K00359 | | 13 | C | | | K00360 | X2 | C | | 050-099 |
| 753 | 22 | | PA | 3-0 | 27-51-11 | K00359 | | 13 | C | | | K00360 | X2 | C | | 150-199, 275-299 |
| 754 | 22 | | PA | 7-10 | 27-51-11 | K00359 | | X1 | C | | | TB0186Y | C003 | BJ | | 050-099 |
| 754 | 22 | | PA | 8-0 | 27-51-11 | K00359 | | X1 | C | | | TB0186Y | C003 | BJ | | 150-199, 275-299 |
| 755 | 14 | | PA | 1-11 | 27-51-11 | K00359 | | A1 | E | | | K00361 | A2 | E | | ALL |
| 756 | 14 | | PA | 2-0 | 27-51-11 | K00359 | | B1 | E | | | K00361 | B2 | E | | ALL |
| 757 | 14 | | PA | 2-2 | 27-51-11 | K00359 | | C1 | E | | | K00361 | C2 | E | | 050-099 |
| 757 | 14 | | PA | 3-0 | 27-51-11 | K00359 | | C1 | E | | | K00361 | C2 | E | | 150-199, 275-299 |
| 758 | 22 | | PA | 8-2 | 27-51-11 | K00360 | | X1 | C | | | TB0186Y | C003 | BJ | | 050-099 |
| 758 | 22 | | PA | 9-0 | 27-51-11 | K00360 | | X1 | C | | | TB0186Y | C003 | BJ | | 150-199, 275-299 |
| 759 | 20 | | PA | 5-1 | 24-31-11 | D00342 | | A3 | | | | TB0200F | A001 | 2 | | 050-099, 150-199 |
| 759 | 20 | | PA | 5-4 | 24-31-11 | D00342 | | A3 | | | | TB0200F | A001 | 2 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 34

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | |
| 760 | 20 | PA | | 5-1 | 24-31-11 | D00342 | | B3 | | | | TB0200F | C001 | 2 | | 050-099, 150-199 |
| 760 | 20 | PA | | 5-4 | 24-31-11 | D00342 | | B3 | | | | TB0200F | C001 | 2 | | 275-299 |
| 761 | 20 | PA | | 5-1 | 24-31-11 | D00342 | | C3 | | | | TB0200F | A002 | 2 | | 050-099, 150-199 |
| 761 | 20 | PA | | 5-4 | 24-31-11 | D00342 | | C3 | | | | TB0200F | A002 | 2 | | 275-299 |
| 762 | 20 | PA | | 2-2 | 30-71-21 | D03966 | | X1 | | | | TB0090Y | C003 | BJ | | 050-099, 150-199 |
| 762 | 22 | PA | | 2-7 | 30-71-21 | D03966 | | X1 | | | | TB0090H | 16 | 2 | | 275-299 |
| 763 | 20 | PA | | 6-7 | 30-71-22 | D03968 | | A2 | | | | TB0186Y | C010 | BJ | | 050-099, 155-199 |
| 763 | 22 | PA | | 2-1 | 30-71-22 | D03968 | | A2 | | | | TB0090Y | A003 | BJ | | 150-154 |
| 763 | 22 | PA | | 2-6 | 30-71-22 | D03968 | | A2 | | | | TB0090Y | A003 | BJ | | 275 |
| 763 | 22 | PA | | 7-0 | 30-71-22 | D03968 | | A2 | | | | TB0186Y | C010 | BJ | | 276-299 |
| 769 | 20 | PA | | 1-7 | 27-51-11 | K00361 | | X2 | | C | | GDX0009 | D.. | F | | 050-099 |
| 769 | 20 | PA | | 2-0 | 27-51-11 | K00361 | | X2 | | C | | GDX0009 | D.. | F | | 150-199, 275-299 |
| 771 | 22 | PA | | 6-4 | 30-71-23 | D05960J | | 7 | | | | TB0186Y | C006 | BJ | | 275 |
| 773 | 12 | PA | | 5-4 | 24-51-52 | D05860J | | 4 | | | | TB5096 | 4 | E | | 050-099, 150-199 |
| 773 | 12 | PA | | 6-3 | 24-51-52 | D05860J | | 4 | | | | TB5096 | 4 | E | | 275-299 |
| 774 | 22 | PA | | 5-4 | 30-71-21 | D05946J | | 1 | | | | TB0188Y | A002 | BJ | | 275-299 |
| 783 | 14 | PA | | 3-11 | 27-51-11 | D05860J | | 1 | | | | K00361 | A1 | E | | ALL |
| 784 | 14 | PA | | 3-11 | 27-51-11 | D05860J | | 2 | | | | K00361 | B1 | E | | ALL |
| 785 | 14 | PA | | 4-0 | 27-51-11 | D05860J | | 3 | | | | K00361 | C1 | E | | ALL |
| 786 | 24 | PK | | 4-1 | 28-42-31 | D05890J | | 5 | | | | D05744J | 3 | | | ALL |
| 787 | 22 | PA | | 4-8 | 28-42-12 | TB0186Y | | A011 | | BJ | | D05744J | 2 | | | 050-099, 150-199 |
| 787 | 22 | PA | | 5-2 | 28-42-12 | TB0186Y | | A011 | | BJ | | D05744J | 2 | | | 275-299 |
| 788 | 18 | PA | | 1-11 | 25-29-11 | D05860J | | 8 | | | | D04928J | 14 | | | ALL |
| 789 | 18 | PA | | 1-11 | 25-29-11 | D05860J | | 9 | | | | D04928J | 16 | | | ALL |
| 790 | 22 | PA | | 2-10 | 28-42-12 | D05890J | | 8 | | | | TB0186Y | A011 | BJ | | 050-099, 150-199 |
| 790 | 22 | PA | | 3-4 | 28-42-12 | D05890J | | 8 | | | | TB0186Y | A011 | BJ | | 275-299 |
| 791 | 24 | PK | | 4-2 | 28-42-12 | D05334J | | 17 | | | | TB0186Y | A011 | BJ | | 050-099, 150-199 |
| 791 | 24 | PK | | 4-7 | 28-42-12 | D05334J | | 17 | | | | TB0186Y | A011 | BJ | | 275-299 |
| 792 | 12 | PA | | 5-2 | 24-51-52 | D05860J | | 5 | | | | TB5096 | 1 | E | | 050-099, 150-199 |
| 792 | 12 | PA | | 6-3 | 24-51-52 | D05860J | | 5 | | | | TB5096 | 1 | E | | 275-299 |
| 793 | 12 | PA | | 5-3 | 24-51-52 | D05860J | | 6 | | | | TB5096 | 2 | E | | 050-099, 150-199 |
| 793 | 12 | PA | | 6-3 | 24-51-52 | D05860J | | 6 | | | | TB5096 | 2 | E | | 275-299 |
| 794 | 12 | PA | | 5-3 | 24-51-52 | D05860J | | 7 | | | | TB5096 | 3 | E | | 050-099, 150-199 |
| 794 | 12 | PA | | 6-3 | 24-51-52 | D05860J | | 7 | | | | TB5096 | 3 | E | | 275-299 |
| 795 | 20 | PA | | 6-3 | 30-71-23 | D05820J | | 14 | | | | TB0090Z | 9 | BJ | | 050-099, 155-199 |
| 795 | 22 | PA | | 6-3 | 30-71-23 | D05820J | | 14 | | | | TB0090Z | 9 | BJ | | 150-154 |
| 795 | 22 | PA | | 6-6 | 30-71-23 | D05820J | | 14 | | | | TB0090Z | 9 | BJ | | 275-299 |
| 797 | 18 | PA | | 5-5 | 25-29-11 | D05744J | | 23 | | | | TB5096 | 6 | E | | 050-099, 150-199 |
| 797 | 18 | PA | | 6-2 | 25-29-11 | D05744J | | 23 | | | | TB5096 | 6 | E | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 35

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 798 | 22 | | PA | | 4-0 | 28-42-11 | D05744J | | | 1 | | | TB0200Y | C005 | BJ | | 050-099, 150-199 |
| 798 | 22 | | PA | | 4-5 | 28-42-11 | D05744J | | | 1 | | | TB0200Y | C005 | BJ | | 275-299 |
| 799 | 20 | | PA | | 1-8 | 30-31-23 | D10190 | | | B2 | | | GDX0002 | D.. | 2 | | ALL |
| 800 | 22 | | PA | | 9-10 | 30-11-11 | D12004 | | | A2 | | | GDX0003 | D.. | 2 | | ALL |
| 801 | 20 | | PA | | 4-8 | 30-71-22 | D05946J | | | 28 | | | TB0188Z | 15 | BJ | | 050-099 |
| 801 | 22 | | PA | | 5-0 | 30-71-22 | D05946J | | | 28 | | | TB0188Y | C001 | BJ | | 150-199 |
| 801 | 22 | | PA | | 5-4 | 30-71-22 | D05946J | | | 28 | | | TB0188Z | 16 | BJ | | 275-299 |
| 802 | 24 | | PK | | 2-7 | 32-09-13 | D01396 | | | X1 | | | TB0090Z | 10 | BJ | | 050-099, 150-199 |
| 802 | 24 | | PK | | 2-10 | 32-09-13 | D01396 | | | X1 | | | TB0090Z | 10 | BJ | | 275-299 |
| 803 | 24 | | PK | | 5-2 | 32-09-13 | D01396 | | | X2 | | | TB0188Y | A003 | BJ | | 050-099, 150-199 |
| 803 | 24 | | PK | | 6-0 | 32-09-13 | D01396 | | | X2 | | | TB0188Y | A003 | BJ | | 275-299 |
| 804 | 24 | | PK | | 6-9 | 32-09-13 | D05668J | | | 6 | | | TB0090Y | C013 | BJ | | 050-099, 150-199 |
| 804 | 24 | | PK | | 6-10 | 32-09-13 | D05668J | | | 6 | | | TB0090Y | C013 | BJ | | 275-299 |
| 805 | 22 | | PQ | H | 4-9 | 27-62-11 | D00630 | | | B2 | | | TB0196Y | A001 | BJ | | 050-099, 150-199 |
| 805 | 22 | | PQ | H | 5-1 | 27-62-11 | D00630 | | | B2 | | | TB0196Y | A001 | BJ | | 275-299 |
| 805Z | | | | H | 0-0 | 27-62-11 | D00630 | | | DED | | | TB0196Y | DED | | | ALL |
| 806 | 22 | | PQ | I | 4-9 | 27-62-11 | D00630 | | | B1 | | | TB0196X | A003 | BJ | | 050-099, 150-199 |
| 806 | 22 | | PQ | I | 5-1 | 27-62-11 | D00630 | | | B1 | | | TB0196X | A003 | BJ | | 275-299 |
| 806Z | | | | I | 0-0 | 27-62-11 | D00630 | | | DED | | | TB0196X | DED | | | ALL |
| 807 | 22 | | PA | | 5-3 | 27-09-12 | D00630 | | | C2 | | | D05668J | 10 | | | ALL |
| 808 | 20 | | PA | | 2-6 | 27-09-12 | D00630 | | | C1 | | | GDX0004 | D.. | 2 | | ALL |
| 809 | 24 | | PK | | 6-7 | 28-22-11 | K00188 | | | X1 | C | | TB0188X | A006 | BJ | | 050-099 |
| 809 | 24 | | PK | | 7-0 | 28-22-11 | K00188 | | | X1 | C | | TB0188X | A006 | BJ | | 150-199, 275-299 |
| 80B | 20 | | PA | | 6-3 | 30-81-11 | D00546 | | | C2 | | | TB0266Z | 12 | BJ | | 050-099, 150-199 |
| 80C | 20 | | PA | | 6-3 | 30-81-11 | D00546 | | | C1 | | | GDX0001 | D.. | 2 | | 050-099, 150-199 |
| 810 | 24 | | PK | | 6-7 | 28-25-11 | D00930 | | | A1 | | | TB0188X | B006 | BJ | | 050-099, 150-199 |
| 810 | 24 | | PK | | 7-0 | 28-25-11 | D00930 | | | A1 | | | TB0188X | B006 | BJ | | 275-299 |
| 811 | 20 | | PA | | 1-4 | 28-25-11 | D00930 | | | A2 | | | GDX0001 | D.. | 2 | | ALL |
| 812 | 20 | | PA | | 1-4 | 28-22-11 | D00930 | | | X2 | | | GDX0001 | A.. | 2 | | ALL |
| 814 | 22 | | PA | | 4-7 | 30-11-11 | D12004 | | | A3 | | | TB0186Y | A014 | BJ | | 050-099 |
| 814 | 22 | | PA | | 4-7 | 30-11-11 | TB0186Y | | | A014 | BJ | | D12004 | A3 | | | 150-199 |
| 814 | 22 | | PA | | 5-2 | 30-11-11 | TB0186Y | | | A014 | BJ | | D12004 | A3 | | | 275-299 |
| 815 | 22 | | PA | | 6-4 | 30-71-21 | D05960J | | | 4 | | | TB0186Y | C011 | BJ | | 275 |
| 816 | 20 | | PA | | 5-0 | 30-71-21 | D05946J | | | 3 | | | TB0188Y | A004 | BJ | | 050-099 |
| 816 | 22 | | PA | | 5-0 | 30-71-21 | D05946J | | | 3 | | | TB0188Y | A004 | BJ | | 150-154 |
| 816 | 20 | | PA | | 4-7 | 30-71-21 | D05946J | | | 3 | | | TB0186Z | 22 | BJ | | 155-199 |
| 816 | 22 | | PA | | 5-4 | 30-71-21 | D05946J | | | 3 | | | TB0188Y | A004 | BJ | | 275-299 |
| 817 | 20 | | PA | | 5-0 | 30-71-21 | D05946J | | | 8 | | | TB0188Y | A004 | BJ | | 050-099 |
| 817 | 22 | | PA | | 5-0 | 30-71-21 | D05946J | | | 8 | | | TB0188Y | A004 | BJ | | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 36

Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 817 | 20 | | PA | 4-7 | 30-71-21 | D05946J | | 8 | | | | | TB0186Z | 22 | BJ | | 155-199 |
| 817 | 22 | | PA | 5-4 | 30-71-21 | D05946J | | 8 | | | | | TB0188Y | A004 | BJ | | 275-299 |
| 818 | 20 | | PA | 6-8 | 30-71-22 | D03968 | | C1 | | | | | TB0186Y | A003 | BJ | | 050-099 |
| 818 | 22 | | PA | 6-8 | 30-71-22 | D03968 | | C1 | | | | | TB0186Y | A003 | BJ | | 150-199 |
| 818 | 22 | | PA | 7-0 | 30-71-22 | D03968 | | C1 | | | | | TB0186Y | A003 | BJ | | 275-299 |
| 819 | 20 | | PA | 5-0 | 30-71-21 | D05946J | | 5 | | | | | TB0188Y | A002 | BJ | | 050-099 |
| 819 | 22 | | PA | 1-5 | 30-71-21 | TB0186Z | | 21 | BJ | | | | TB0188Y | C004 | BJ | | 150-154 |
| 819 | 20 | | PA | 1-5 | 30-71-21 | TB0186Z | | 21 | BJ | | | | TB0188Y | C004 | BJ | | 155-199 |
| 819 | 22 | | PA | 5-4 | 30-71-21 | D05946J | | 5 | | | | | TB0188Y | C004 | BJ | | 275-299 |
| 820 | 20 | | PA | 4-7 | 30-71-21 | D05946J | | 4 | | | | | TB0186Z | 21 | BJ | | 150-199 |
| 820 | 22 | | PA | 5-4 | 30-71-21 | D05946J | | 4 | | | | | TB0188Y | C004 | BJ | | 275-299 |
| 821 | 20 | | PA | 8-7 | 30-71-22 | C01150 | | 1 | D | | | | D03968 | C2 | | | 150-154 |
| 821 | 20 | | PA | 6-1 | 30-71-22 | D05960J | | 5 | | | | | D03968 | C2 | | | 275 |
| 822 | 20 | | PA | 3-2 | 30-71-22 | D05690J | | 17 | | | | | TB0188Y | C001 | BJ | | 050-099 |
| 822 | 22 | | PA | 5-0 | 30-71-22 | TB0188Y | | C001 | BJ | | | | D05946J | 16 | | | 150-199 |
| 822 | 22 | | PA | 3-6 | 30-71-22 | D05690J | | 17 | | | | | TB0188Y | C001 | BJ | | 275-299 |
| 824 | 20 | | PA | 2-10 | 30-71-22 | D05690J | | 1 | | | | | TB0188Z | 16 | BJ | | 050-099 |
| 824 | 22 | | PA | 2-10 | 30-71-22 | D05690J | | 1 | | | | | TB0188Z | 15 | BJ | | 150-154 |
| 824 | 20 | | PA | 2-10 | 30-71-22 | D05690J | | 1 | | | | | TB0188Z | 15 | BJ | | 155-199 |
| 824 | 22 | | PA | 3-6 | 30-71-22 | D05690J | | 1 | | | | | TB0188Y | C001 | BJ | | 275-299 |
| 825 | 24 | | PK | 2-7 | 30-34-21 | D03946 | | X1 | | | | | TB0090Y | C011 | BJ | | 050-099, 150-199 |
| 826 | 22 | | PA | 6-4 | 30-71-23 | D05960J | | 2 | | | | | TB0186Z | 7 | BJ | | 275 |
| 828 | 20 | | PA | 6-2 | SPARE | D05960J | | 6 | | | | | TB0090Y | A003 | BJ | | 150-154 |
| 828 | 20 | | PA | 6-7 | 30-71-22 | D05960J | | 6 | | | | | TB0090Y | A003 | BJ | | 275 |
| 829 | 20 | | PA | 4-8 | 30-71-22 | D05946J | | 18 | | | | | TB0188Z | 15 | BJ | | 050-099, 155-199 |
| 829 | 22 | | PA | 4-8 | 30-71-22 | D05946J | | 18 | | | | | TB0188Z | 15 | BJ | | 150-154 |
| 829 | 22 | | PA | 5-4 | 30-71-22 | D05946J | | 18 | | | | | TB0188Z | 16 | BJ | | 275-299 |
| 831 | 22 | | PA | 4-8 | 30-71-22 | D05946J | | 15 | | | | | TB0188Z | 16 | BJ | | 150-199 |
| 832 | 22 | | PA | 2-6 | 30-34-21 | D10232 | | A2 | | | | | TB0090Y | A013 | BJ | | 050-099, 150-199 |
| 832 | 22 | | PA | 2-8 | 30-34-21 | D10232 | | A2 | | | | | TB0090Y | A013 | BJ | | 275-299 |
| 838 | 22 | | PA | 6-1 | 30-71-22 | D03968 | | D2 | | | | | D05960J | 1 | | | 275 |
| 840 | 24 | | PK | 4-10 | 73-21-12 | D05668J | | 8 | | | | | D03946 | A2 | | | 050-099, 275-299 |
| 840 | 24 | | PK | 4-10 | 73-21-12 | D03946 | | A2 | | | | | D05668J | 8 | | | 150-199 |
| 841 | 22 | | PA | 4-7 | 30-33-11 | D00628 | | C1 | | | | | TB0196X | C015 | BJ | | 050-099, 150-199 |
| 841 | 22 | | PA | 5-3 | 30-33-11 | D00628 | | C1 | | | | | TB0196X | C015 | BJ | | 275-299 |
| 842 | 22 | | PA | 6-0 | 30-33-11 | D00628 | | C3 | | | | | TB0188Y | A009 | BJ | | 050-099, 150-199 |
| 842 | 22 | | PA | 6-5 | 30-33-11 | D00628 | | C3 | | | | | TB0188Y | A009 | BJ | | 275-299 |
| 843 | 24 | | PK | 2-7 | 30-32-21 | D00468 | | X1 | | | | | TB0090Z | 7 | BJ | | 050-099, 150-199 |
| 843 | 24 | | PK | 2-11 | 30-32-21 | D00468 | | X1 | | | | | TB0090Z | 7 | BJ | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 37

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|--------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | |
| 844 | 20 | | PA | | 2-7 | 30-32-21 | D00468 | | X2 | | GDX0001 | D.. | 2 | | ALL |
| 845 | 22 | | PA | | 1-9 | 30-32-21 | D10190 | | C1 | | TB0090Y | A006 | BJ | | 050-099, 150-199 |
| 845 | 22 | | PA | | 2-1 | 30-32-21 | D10190 | | C1 | | TB0090Y | A006 | BJ | | 275-299 |
| 846 | 20 | | PA | | 2-7 | 30-32-21 | D00468 | | B1 | | GDX0001 | A.. | 2 | | ALL |
| 847 | 20 | | PQ | F | 2-7 | 30-32-21 | D00468 | | B2 | | GDX0001 | D.. | 2 | | ALL |
| 847Z | | | | F | 0-0 | 30-32-21 | D00468 | | DED | | GDX0001 | DED | | | ALL |
| 848 | 22 | | PA | | 6-0 | 30-32-21 | D00468 | | C1 | | D05648J | 9 | | | ALL |
| 850 | 22 | | PQ | G | 4-4 | 30-32-21 | D00468 | | D2 | | TB0196Y | C012 | BJ | | 050-099, 150-199 |
| 850 | 22 | | PQ | G | 4-10 | 30-32-21 | D00468 | | D2 | | TB0196Y | C012 | BJ | | 275-299 |
| 850Z | | | | G | 0-0 | 30-32-21 | D00468 | | DED | | TB0196Y | DED | | | ALL |
| 851 | 22 | | PA | | 2-4 | 30-34-21 | D10232 | | A1 | | TB0090Y | A005 | BJ | | 050-099, 150-199 |
| 851 | 22 | | PA | | 2-8 | 30-34-21 | D10232 | | A1 | | TB0090Y | A005 | BJ | | 275-299 |
| 853 | 22 | | PA | | 5-4 | 30-71-22 | D05946J | | 16 | | TB0188Z | 16 | BJ | | 275-299 |
| 854 | 22 | | PA | | 6-4 | 30-32-21 | D05908J | | 18 | | TB0090Y | C005 | BJ | | 050-099, 150-199 |
| 854 | 22 | | PA | | 6-8 | 30-32-21 | D05908J | | 18 | | TB0090Y | C005 | BJ | | 275-299 |
| 855 | 22 | | PA | | 2-11 | 30-32-21 | D00628 | | A3 | | TB0090Y | A006 | BJ | | 050-099, 150-199 |
| 855 | 22 | | PA | | 3-3 | 30-32-21 | D00628 | | A3 | | TB0090Y | A006 | BJ | | 275-299 |
| 856 | 22 | | PA | | 2-11 | 30-32-21 | D00628 | | A2 | | TB0090Y | C005 | BJ | | 050-099, 150-199 |
| 856 | 22 | | PA | | 3-3 | 30-32-21 | D00628 | | A2 | | TB0090Y | C005 | BJ | | 275-299 |
| 860 | 22 | | PQ | AE | 4-8 | 30-33-11 | D00546 | | B2 | | TB0196X | A015 | BJ | | 050-099, 150-199 |
| 860 | 22 | | PQ | AE | 5-4 | 30-33-11 | D00546 | | B2 | | TB0196X | A015 | BJ | | 275-299 |
| 860Z | | | | AE | 0-0 | 30-33-11 | D00546 | | DED | | TB0196X | DED | | | ALL |
| 861 | 22 | | PQ | AF | 4-8 | 30-33-11 | D00546 | | B3 | | TB0196X | B015 | BJ | | 050-099, 150-199 |
| 861 | 22 | | PQ | AF | 5-4 | 30-33-11 | D00546 | | B3 | | TB0196X | B015 | BJ | | 275-299 |
| 861Z | | | | AF | 0-0 | 30-33-11 | D00546 | | DED | | TB0196X | DED | | | ALL |
| 862 | 22 | | PA | | 6-8 | 30-33-11 | D05648J | | 49 | | TB0186Y | A013 | BJ | | 050-099, 150-199 |
| 862 | 22 | | PA | | 7-2 | 30-33-11 | D05648J | | 49 | | TB0186Y | A013 | BJ | | 275-299 |
| 863 | 24 | | PK | | 4-1 | 30-33-11 | D05334J | | 9 | | TB0186Y | A013 | BJ | | 050-099, 150-199 |
| 863 | 24 | | PK | | 4-7 | 30-33-11 | D05334J | | 9 | | TB0186Y | A013 | BJ | | 275-299 |
| 864 | 22 | | PA | | 6-7 | 30-11-11 | D05648J | | 33 | | D00914 | D1 | | | 050-099 |
| 864 | 22 | | PA | | 6-7 | 30-11-11 | D00914 | | D1 | | D05648J | 33 | | | 150-199 |
| 864 | 22 | | PA | | 11-2 | 30-11-11 | D00914 | | D1 | | TB0268Y | A006 | BJ | | 275-299 |
| 865 | 22 | | PQ | J | 10-0 | 27-62-11 | D05668J | | 18 | | TB0090G | 20 | 2 | | 050-099, 150-199 |
| 865 | 22 | | PQ | J | 5-5 | 27-62-11 | D05668J | | 18 | | TB0090G | 20 | 2 | | 275-299 |
| 865Z | | | | J | 0-0 | 27-62-11 | D05668J | | DED | | TB0090G | DED | | | ALL |
| 866 | 16 | | PA | | 5-2 | 33-45-11 | D05650J | | 1 FM | | TB0196F | A009 | 2 | | 050-099 |
| 866 | 16 | | PA | | 5-2 | 33-45-11 | TB0196F | | A009 2 | | D05650J | 1 FM | | | 150-199 |
| 866 | 16 | | PA | | 6-2 | 33-45-11 | TB0196F | | A009 2 | | D05650J | 1 FM | | | 275-299 |
| 867 | 16 | | PA | | 5-2 | 33-45-11 | D05650J | | 4 FM | | TB0196F | C009 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 38

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | |
| 867 | 16 | | PA | 5-2 | 33-45-11 | TB0196F | C009 | | 2 | | D05650J | 4 | FM | | 150-199 | |
| 867 | 16 | | PA | 6-2 | 33-45-11 | TB0196F | C009 | | 2 | | D05650J | 4 | FM | | 275-299 | |
| 868 | 22 | | PA | 4-8 | 30-31-23 | D00624 | | A3 | | | D05960J | 10 | | | ALL | |
| 873 | 20 | | PA | 2-6 | 30-32-21 | D00468 | | D1 | | | GDX0002 | S.. | 2 | | ALL | |
| 875 | 20 | | PA | 2-4 | 30-34-21 | D03946 | | D1 | | | GDX0002 | S.. | 2 | | ALL | |
| 876 | 20 | | PA | 2-11 | 30-31-21 | D03938 | | D1 | | | GDX0002 | S.. | 2 | | ALL | |
| 878 | 20 | | PA | 5-0 | 30-71-22 | D05946J | | | 16 | | TB0188Y | C001 | BJ | | 050-099 | |
| 879 | 20 | | PA | 5-0 | 30-71-22 | D05946J | | | 17 | | TB0186Y | A003 | BJ | | 050-099 | |
| 879 | 22 | | PA | 4-8 | 30-71-22 | D05946J | | | 17 | | TB0188Z | 16 | BJ | | 150-199 | |
| 879 | 22 | | PA | 5-4 | 30-71-22 | D05946J | | | 17 | | TB0188Z | 16 | BJ | | 275-299 | |
| 880 | 20 | | PA | 2-10 | 30-71-22 | D05690J | | | 25 | | TB0188Z | 16 | BJ | | 050-099 | |
| 880 | 22 | | PA | 3-6 | 30-71-22 | D05690J | | | 25 | | TB0188Z | 15 | BJ | | 275-299 | |
| 882 | 20 | | PA | 4-8 | 30-71-22 | D05946J | | | 13 | | TB0188Z | 15 | BJ | | 050-099 | |
| 882 | 22 | | PA | 4-8 | 30-71-22 | D05946J | | | 13 | | TB0188Z | 16 | BJ | | 150-199 | |
| 882 | 22 | | PA | 5-4 | 30-71-22 | D05946J | | | 13 | | TB0188Z | 15 | BJ | | 275-299 | |
| 883 | 22 | | PA | 4-8 | 30-71-22 | D05946J | | | 14 | | TB0188Z | 15 | BJ | | 150-154 | |
| 883 | 20 | | PA | 4-8 | 30-71-22 | D05946J | | | 14 | | TB0188Z | 15 | BJ | | 155-199 | |
| 883 | 22 | | PA | 5-4 | 30-71-22 | D05946J | | | 14 | | TB0188Z | 16 | BJ | | 275-299 | |
| 884 | 22 | | PA | 6-0 | 27-51-11 | D05668J | | | 19 | | D10016 | X2 | | | ALL | |
| 885 | 20 | | PA | 2-2 | 27-51-11 | D10016 | | A2 | | | D03908 | B3 | | | ALL | |
| 886 | 22 | | PA | 6-1 | 27-51-11 | D10016 | | X1 | | | TB0188G | 10 | 2 | | 050-099, 150-199 | |
| 886 | 22 | | PA | 6-7 | 27-51-11 | D10016 | | X1 | | | TB0188G | 10 | 2 | | 275-299 | |
| 887 | 20 | | PA | 5-0 | 30-71-23 | D05820J | | | 4 | | TB0188Z | 23 | BJ | | 050-099 | |
| 887 | 20 | | PA | 5-0 | 30-71-23 | D05820J | | | 6 | | TB0188Z | 24 | BJ | | 150-199 | |
| 887 | 22 | | PA | 6-3 | 30-71-23 | D05820J | | | 6 | | TB0186Y | A006 | BJ | | 275-299 | |
| 888 | 24 | | PK | 4-0 | 24-51-52 | D05668J | | | 20 | | M01084 | A | C | | 050-099, 155-199, 275-299 | |
| 888 | 24 | | PK | 7-0 | 24-51-52 | D05668J | | | 20 | | M01084 | A | C | | 150-154 | |
| 889 | 24 | | PK | 5-1 | 24-51-52 | D05668J | | | 21 | | TB0196X | C004 | BJ | | 050-099, 150-199 | |
| 889 | 24 | | PK | 5-5 | 24-51-52 | D05668J | | | 21 | | TB0196X | C004 | BJ | | 275-299 | |
| 890 | 22 | | PA | 9-7 | 30-11-11 | D00914 | | | B2 | | D12002 | X2 | | | ALL | |
| 891 | 22 | | PA | 9-7 | 30-11-11 | D00914 | | | C2 | | D12004 | X2 | | | ALL | |
| 892 | 24 | | PK | 4-1 | 30-11-11 | D05334J | | | 12 | | TB0186Y | A014 | BJ | | 050-099, 150-199 | |
| 892 | 24 | | PK | 4-7 | 30-11-11 | D05334J | | | 12 | | TB0186Y | A014 | BJ | | 275-299 | |
| 893 | 24 | | PK | 4-1 | 30-11-11 | D05334J | | | 14 | | TB0186Y | C013 | BJ | | 050-099, 150-199 | |
| 893 | 24 | | PK | 4-7 | 30-11-11 | D05334J | | | 14 | | TB0186Y | C013 | BJ | | 275-299 | |
| 894 | 22 | | PA | 5-5 | 30-31-11 | D05908J | | | 19 | | TB0188Y | A011 | BJ | | 050-099, 150-199 | |
| 894 | 22 | | PA | 6-5 | 30-31-11 | D05908J | | | 19 | | TB0188Y | A011 | BJ | | 275-299 | |
| 895 | 24 | | PK | 3-4 | 30-31-11 | D10184 | | | B2 | | D05334J | 4 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 39

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0142 | 286T0142 | | | P33-R2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | |
| 896 | 24 | | PK | 4-1 | 30-31-11 | D05334J | | 3 | | | TB0188Y | A011 | BJ | | 050-099, 150-199 |
| 896 | 24 | | PK | 4-7 | 30-31-11 | D05334J | | 3 | | | TB0188Y | A011 | BJ | | 275-299 |
| 897 | 24 | | PV K | 4-4 | 30-31-11 | D10184 | | X2 | | | TB0200X | A003 | BJ | | 050-099, 150-199 |
| 897 | 24 | | PV K | 4-8 | 30-31-11 | D10184 | | X2 | | | TB0200X | A003 | BJ | | 275-299 |
| 897Z | | | | 0-0 | 30-31-11 | D10184 | | DED | | | TB0200X | DED | | | ALL |
| 898 | 24 | | PK | 5-2 | 30-31-11 | D10184 | | B3 | | | TB0186X | B002 | BJ | | 050-099, 150-199 |
| 898 | 24 | | PK | 5-5 | 30-31-11 | D10184 | | B3 | | | TB0186X | B002 | BJ | | 275-299 |
| 899 | 24 | | PV L | 5-2 | 30-31-11 | D10184 | | X1 | | | TB0186X | C002 | BJ | | 050-099, 150-199 |
| 899 | 24 | | PV L | 5-5 | 30-31-11 | D10184 | | X1 | | | TB0186X | C002 | BJ | | 275-299 |
| 899Z | | | | 0-0 | 30-31-11 | D10184 | | DED | | | TB0186X | DED | | | ALL |
| FRA | | | | 0-0 | 78-34-11 | TB0266X | | | AA | | TB0266X | B009 | BJ | | ALL |
| FRC | | | | 0-0 | 78-34-21 | D05668J | | 39 | | | D05668J | | | AC | ALL |
| PA1 | | | | 0-0 | 99-99-99 | D00792 | | G2 | | | D00792 | G3 | | | ALL |
| W0143 | 286T0143 | | | E2-2 R,SHELF | | | | | | | | | | | |
| 001 | 24 | | PK | 5-0 | 34-61-13 | D05713J | | 1 | | | TB0133F | A175 | 2 | | ALL |
| 002 | 22 | | PA | 5-0 | 34-61-13 | D05713J | | 11 | | | TB0133F | C180 | 2 | | ALL |
| 009 | 24 | | PK | 4-0 | 34-33-21 | D05861P | | 21 | | | D05575P | 4 | | | ALL |
| 010 | 24 | | PK | 4-0 | 22-12-21 | D05861P | | 15 | | | D05575P | 6 | | | ALL |
| 011 | 24 | | PK | 4-0 | 34-61-25 | D05713J | | 54 | | | TB0133G | 103 | 2 | | ALL |
| 017 | 24 | | PK | 4-0 | 34-53-13 | D05713J | | 27 | | | TB0133G | 115 | 2 | | ALL |
| 201B | 24 | | PW IA | 4-0 | 34-61-11 | D05425P | | 6 | | | TB0133G | 182 | 2 | | ALL |
| 201R | 24 | | PW IA | 0-0 | 34-61-11 | D05425P | | 5 | | | TB0133G | 181 | 2 | | ALL |
| 201Z | | | | 0-0 | 34-61-11 | D05425P | | 4 | | | GDY0012 | S.. | 2 | | ALL |
| 202B | 24 | | PW IB | 5-0 | 34-61-13 | D05713J | | 3 | | | TB0133F | C171 | 2 | | ALL |
| 202R | 24 | | PW IB | 0-0 | 34-61-13 | D05713J | | 2 | | | TB0133F | A171 | 2 | | ALL |
| 202Z | | | | 0-0 | 34-61-13 | D05713J | | 4 | | | GDY0011 | S.. | 2 | | ALL |
| 203B | 24 | | PW IC | 5-0 | 34-61-13 | D05713J | | 6 | | | TB0133F | C172 | 2 | | ALL |
| 203R | 24 | | PW IC | 0-0 | 34-61-13 | D05713J | | 5 | | | TB0133F | A172 | 2 | | ALL |
| 203Z | | | | 0-0 | 34-61-13 | D05713J | | 7 | | | GDY0011 | S.. | 2 | | ALL |
| 204B | 24 | | PW ID | 5-0 | 34-61-13 | D05713J | | 9 | | | TB0133F | C173 | 2 | | ALL |
| 204R | 24 | | PW ID | 0-0 | 34-61-13 | D05713J | | 8 | | | TB0133F | A173 | 2 | | ALL |
| 204Z | | | | 0-0 | 34-61-13 | D05713J | | 10 | | | GDY0011 | S.. | 2 | | ALL |
| 205B | 24 | | PW IE | 5-0 | 34-61-13 | D05713J | | 13 | | | TB0133F | C174 | 2 | | ALL |
| 205R | 24 | | PW IE | 0-0 | 34-61-13 | D05713J | | 12 | | | TB0133F | A174 | 2 | | ALL |
| 205Z | | | | 0-0 | 34-61-13 | D05713J | | 14 | | | GDY0011 | S.. | 2 | | ALL |
| 208B | 24 | | PW IH | 4-0 | 34-61-11 | D05713J | | 19 | | | TB0133F | C037 | 2 | | ALL |
| 208R | 24 | | PW IH | 0-0 | 34-61-11 | D05713J | | 18 | | | TB0133F | A037 | 2 | | ALL |
| 208Z | | | | 0-0 | 34-61-11 | D05713J | | 20 | | | GDY0007 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 40

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0143 | 286T0143 | | | E2-2 R,SHELF (continued) | | | | | | | | | | | | | |
| 210B | 24 | PW | IJ | 5-0 | 34-61-11 | D05713J | | 25 | | | | | TB0133F | C177 | 2 | | ALL |
| 210R | 24 | PW | IJ | 0-0 | 34-61-11 | D05713J | | 24 | | | | | TB0133F | A177 | 2 | | ALL |
| 210Z | | | IJ | 0-0 | 34-61-11 | D05713J | | 26 | | | | | GDY0012 | S.. | 2 | | ALL |
| 211B | 24 | PW | IK | 5-0 | 34-53-21 | D05713J | | 21 | | | | | TB0133H | 71 | 2 | | ALL |
| 211R | 24 | PW | IK | 0-0 | 34-53-21 | D05713J | | 22 | | | | | TB0133H | 69 | 2 | | ALL |
| 211Z | | | IK | 0-0 | 34-53-21 | D05713J | | 23 | | | | | GDY0011 | S.. | 2 | | ALL |
| 213 | 20 | UA | | 1-6 | 34-22-29 | TB0133H | | REF | | | IM | | GDY0007 | S.. | 2 | | 050-099, 150-151, 155-199 |
| 213B | 24 | PW | IM | 5-0 | 34-22-29 | D05861P | | 7 | | | | | TB0133H | 59 | 2 | | ALL |
| 213R | 24 | PW | IM | 0-0 | 34-22-29 | D05861P | | 6 | | | | | TB0133H | 57 | 2 | | ALL |
| 213Z | | | IM | 0-0 | 34-22-29 | D05861P | | 8 | | | | | TB0133H | REF | | IM | 050-099, 150-151, 155-199 |
| 213Z | | | IM | 0-0 | 34-22-29 | D05861P | | 8 | | | | | GDY0009 | S.. | 2 | | 152-154, 275-299 |
| 214 | 20 | UA | | 1-6 | 34-33-21 | TB0133H | | REF | | | IN | | GDY0007 | S.. | 2 | | 050-099, 155-199, 277-299 |
| 214B | 24 | PW | IN | 5-0 | 34-33-21 | D05575P | | 3 | | | | | TB0133H | 59 | 2 | | ALL |
| 214R | 24 | PW | IN | 0-0 | 34-33-21 | D05575P | | 2 | | | | | TB0133H | 57 | 2 | | ALL |
| 214Z | | | IN | 0-0 | 34-33-21 | D05575P | | 1 | | | | | TB0133H | REF | | IN | 050-099, 155-199, 277-299 |
| 214Z | | | IN | 0-0 | 34-33-21 | D05575P | | 1 | | | | | GDY0009 | S.. | 2 | | 150-154, 275-276 |
| 215B | 24 | PW | IO | 4-0 | 22-12-21 | D05861P | | 17 | | | | | D05575P | 8 | | | ALL |
| 215R | 24 | PW | IO | 0-0 | 22-12-21 | D05861P | | 16 | | | | | D05575P | 7 | | | ALL |
| 215Z | | | IO | 0-0 | 22-12-21 | D05861P | | 18 | | | | | D05575P | 9 | | | ALL |
| 218B | 24 | PW | IR | 4-0 | 34-22-28 | D05861P | | 23 | | | | | D05575P | 20 | | | ALL |
| 218R | 24 | PW | IR | 0-0 | 34-22-28 | D05861P | | 22 | | | | | D05575P | 19 | | | ALL |
| 218Z | | | IR | 0-0 | 34-22-28 | D05861P | | 24 | | | | | D05575P | 21 | | | ALL |
| 220B | 24 | PW | IT | 5-0 | 34-61-26 | D05713J | | 30 | | | | | TB0133Z | 81 | BJ | | 050-099, 150-156, 162-166 |
| 220B | 24 | PW | IT | 4-0 | 34-61-26 | D05713J | | 30 | | | | | TB0133Y | C003 | BJ | | 157, 167-199, 277-299 |
| 220B | 24 | PW | IT | 4-0 | 34-61-26 | D05713J | | 30 | | | | | TB0133Y | C03 | BJ | | 275-276 |
| 220R | 24 | PW | IT | 0-0 | 34-61-26 | D05713J | | 29 | | | | | TB0133Z | 80 | BJ | | 050-099, 150-156, 162-166 |
| 220R | 24 | PW | IT | 0-0 | 34-61-26 | D05713J | | 29 | | | | | TB0133Y | A003 | BJ | | 157, 167-199, 277-299 |
| 220R | 24 | PW | IT | 0-0 | 34-61-26 | D05713J | | 29 | | | | | TB0133Y | A03 | BJ | | 275-276 |
| 220Z | | | IT | 0-0 | 34-61-26 | D05713J | | 31 | | | | | GDY0012 | S.. | 2 | | 050-099, 150-156, 162-166 |
| 220Z | | | IT | 0-0 | 34-61-26 | D05713J | | 31 | | | | | GDY0001 | S.. | 2 | | 157, 167-199, 275-299 |
| 221 | 20 | UA | | 1-6 | 31-35-11 | TB0133X | | REF | | | IU | | GDY0008 | S.. | 2 | | 050-099, 155-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 41

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0143 | 286T0143 | | | E2-2 R,SHELF (continued) | | | | | | | | | | | |
| 221B | 24 | PW | IU | | 4-0 | 31-35-11 | D05763J | | | | TB0133X | B159 | BJ | | ALL |
| 221R | 24 | PW | IU | | 0-0 | 31-35-11 | D05763J | | | | TB0133X | A159 | BJ | | ALL |
| 221Z | | | IU | | 0-0 | 31-35-11 | D05763J | | | | TB0133X | REF | | IU | 050-099, 155-199, 275-299 |
| 221Z | | | IU | | 0-0 | 31-35-11 | D05763J | | | 18 | GDY0010 | S.. | 2 | | 150-154 |
| 226B | 24 | PW | JA | | 4-0 | 31-35-11 | D05425P | | | 2 | TB0133Y | C164 | BJ | | ALL |
| 226R | 24 | PW | JA | | 0-0 | 31-35-11 | D05425P | | | 1 | TB0133Y | A164 | BJ | | ALL |
| 226Z | | | JA | | 0-0 | 31-35-11 | D05425P | | | 3 | GDY0010 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 226Z | | | JA | | 0-0 | 31-35-11 | D05425P | | | 3 | GDY0011 | S.. | 2 | | 150-154 |
| 227B | 24 | PW | JB | | 5-0 | 31-35-13 | D05861P | | | 14 | TB0133X | B049 | BJ | | ALL |
| 227R | 24 | PW | JB | | 0-0 | 31-35-13 | D05861P | | | 13 | TB0133X | A049 | BJ | | ALL |
| 227Z | | | JB | | 0-0 | 31-35-13 | D05861P | | | 4 | GDY0008 | S.. | 2 | | ALL |
| 228B | 24 | PW | JC | | 4-0 | 31-35-13 | D05713J | | | 36 | TB0133X | D049 | BJ | | ALL |
| 228R | 24 | PW | JC | | 0-0 | 31-35-13 | D05713J | | | 35 | TB0133X | C049 | BJ | | ALL |
| 228Z | | | JC | | 0-0 | 31-35-13 | D05713J | | | 37 | GDY0008 | S.. | 2 | | ALL |
| 229B | 24 | PW | JD | | 4-0 | 31-35-13 | D05713J | | | 39 | TB0133X | B050 | BJ | | ALL |
| 229R | 24 | PW | JD | | 0-0 | 31-35-13 | D05713J | | | 38 | TB0133X | A050 | BJ | | ALL |
| 229Z | | | JD | | 0-0 | 31-35-13 | D05713J | | | 40 | GDY0008 | S.. | 2 | | ALL |
| 230B | 24 | PW | JE | | 4-0 | 31-35-13 | D05713J | | | 16 | TB0133X | D050 | BJ | | ALL |
| 230R | 24 | PW | JE | | 0-0 | 31-35-13 | D05713J | | | 15 | TB0133X | C050 | BJ | | ALL |
| 230Z | | | JE | | 0-0 | 31-35-13 | D05713J | | | 17 | GDY0008 | S.. | 2 | | ALL |
| 231B | 24 | PW | JF | | 5-0 | 31-35-13 | D05575P | | | 12 | TB0133X | B052 | BJ | | ALL |
| 231R | 24 | PW | JF | | 0-0 | 31-35-13 | D05575P | | | 11 | TB0133X | A052 | BJ | | ALL |
| 231Z | | | JF | | 0-0 | 31-35-13 | D05575P | | | 13 | GDY0009 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 231Z | | | JF | | 0-0 | 31-35-13 | D05575P | | | 13 | GDY0008 | S.. | 2 | | 150-154 |
| 232B | 24 | PW | JG | | 3-0 | 34-61-26 | D05713J | | | 52 | TB0133Y | C130 | BJ | | ALL |
| 232R | 24 | PW | JG | | 0-0 | 34-61-26 | D05713J | | | 51 | TB0133Y | A130 | BJ | | ALL |
| 232Z | | | JG | | 0-0 | 34-61-26 | D05713J | | | 53 | GDY0006 | S.. | 2 | | ALL |
| 233B | 24 | PW | JH | | 4-0 | 31-36-11 | D05763J | | | 41 | TB0133Z | 48 | BJ | | ALL |
| 233R | 24 | PW | JH | | 0-0 | 31-36-11 | D05763J | | | 40 | TB0133Z | 47 | BJ | | ALL |
| 233Z | | | JH | | 0-0 | 31-36-11 | D05763J | | | 42 | GDY0008 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 233Z | | | JH | | 0-0 | 31-36-11 | D05763J | | | 42 | GDY0007 | S.. | 2 | | 150-154 |
| 237B | 24 | PW | JL | | 4-0 | 34-61-26 | D05425P | | | 8 | TB0133Y | C077 | BJ | | ALL |
| 237R | 24 | PW | JL | | 0-0 | 34-61-26 | D05425P | | | 7 | TB0133Y | A077 | BJ | | ALL |
| 237Z | | | JL | | 0-0 | 34-61-26 | D05425P | | | 9 | GDY0012 | S.. | 2 | | ALL |
| 238B | 24 | PW | JM | | 5-0 | 34-61-26 | D05713J | | | 42 | TB0133H | 190 | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 42
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0143 | 286T0143 | | | E2-2 R,SHELF (continued) | | | | | | | | | | | | | |
| 238R | 24 | PW | JM | 0-0 | 34-61-26 | D05713J | | 41 | | | | | TB0133H | 188 | 2 | | ALL |
| 238Z | | | JM | 0-0 | 34-61-26 | D05713J | | 43 | | | | | GDY0013 | S.. | 2 | | ALL |
| 239B | 24 | PW | JN | 4-0 | 31-31-20 | TB0133H | | 59 | 2 | | | | D05713J | 45 | | | ALL |
| 239R | 24 | PW | JN | 0-0 | 31-31-20 | TB0133H | | 57 | 2 | | | | D05713J | 44 | | | ALL |
| 239Z | | | JN | 0-0 | 31-31-20 | GDY0009 | | S.. | 2 | | | | D05713J | 46 | | | ALL |
| 240B | 24 | PW | JQ | 6-0 | 34-61-15 | D05763J | | 44 | | | | | TB0133Z | 18 | BJ | | ALL |
| 240R | 24 | PW | JQ | 0-0 | 34-61-15 | D05763J | | 43 | | | | | TB0133Z | 17 | BJ | | ALL |
| 240Z | | | JQ | 0-0 | 34-61-15 | D05763J | | 45 | | | | | GDY0002 | S.. | 2 | | ALL |
| 243 | 20 | UA | | 1-6 | 31-41-33 | TB0133H | | REF | | JR | | | GDY0007 | S.. | 2 | | 050-099, 155-199, 277-299 |
| 243B | 24 | PW | JR | 4-0 | 31-41-33 | D05713J | | 48 | | | | | TB0133H | 59 | 2 | | ALL |
| 243R | 24 | PW | JR | 0-0 | 31-41-33 | D05713J | | 47 | | | | | TB0133H | 57 | 2 | | ALL |
| 243Z | | | JR | 0-0 | 31-41-33 | D05713J | | 49 | | | | | TB0133H | REF | | JR | 050-099, 155-199, 277-299 |
| 243Z | | | JR | 0-0 | 31-41-33 | D05713J | | 49 | | | | | GDY0009 | S.. | 2 | | 150-154, 275-276 |
| 245B | 24 | PW | JT | 4-0 | 34-61-25 | D05763J | | 2 | | | | | TB0133H | 190 | 2 | | ALL |
| 245R | 24 | PW | JT | 0-0 | 34-61-25 | D05763J | | 1 | | | | | TB0133H | 188 | 2 | | ALL |
| 245Z | | | JT | 0-0 | 34-61-25 | D05763J | | 3 | | | | | GDY0013 | S.. | 2 | | ALL |
| 248B | 24 | PW | JW | 7-0 | 22-21-31 | TB0133Z | | 23 | BJ | | | | D06261J | 2 | | | 150-199, 275-299 |
| 248R | 24 | PW | JW | 0-0 | 22-21-31 | TB0133Z | | 24 | BJ | | | | D06261J | 1 | | | 150-199, 275-299 |
| 248Z | | | JW | 0-0 | 22-21-31 | D06261J | | 3 | | | | | GDY0003 | S.. | 2 | | 150-199, 275-299 |
| 501B | 24 | PW | UA | 3-0 | 31-35-12 | D05763J | | 5 | | | | | TB0133X | B085 | BJ | | 050-099, 155-199, 275-299 |
| 501B | 24 | PW | UA | 4-0 | 31-35-12 | D05763J | | 5 | | | | | TB0133X | D159 | BJ | | 150-154 |
| 501R | 24 | PW | UA | 0-0 | 31-35-12 | D05763J | | 4 | | | | | TB0133X | A085 | BJ | | 050-099, 155-199, 275-299 |
| 501R | 24 | PW | UA | 0-0 | 31-35-12 | D05763J | | 4 | | | | | TB0133X | C159 | BJ | | 150-154 |
| 501Z | | | UA | 0-0 | 31-35-12 | D05763J | | 6 | | | | | GDY0013 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 501Z | | | UA | 0-0 | 31-35-12 | D05763J | | 6 | | | | | GDY0010 | S.. | 2 | | 150-154 |
| 502B | 24 | PW | UB | 3-0 | 31-35-12 | D05763J | | 8 | | | | | TB0133X | D085 | BJ | | 050-099, 155-199, 275-299 |
| 502B | 24 | PW | UB | 4-0 | 31-35-12 | D05763J | | 8 | | | | | TB0133X | B160 | BJ | | 150-154 |
| 502R | 24 | PW | UB | 0-0 | 31-35-12 | D05763J | | 7 | | | | | TB0133X | C085 | BJ | | 050-099, 155-199, 275-299 |
| 502R | 24 | PW | UB | 0-0 | 31-35-12 | D05763J | | 7 | | | | | TB0133X | A160 | BJ | | 150-154 |
| 502Z | | | UB | 0-0 | 31-35-12 | D05763J | | 9 | | | | | GDY0013 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 502Z | | | UB | 0-0 | 31-35-12 | D05763J | | 9 | | | | | GDY0010 | S.. | 2 | | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 43

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0143 | 286T0143 | | | E2-2 R,SHELF (continued) | | | | | | | | | | | |
| 503B | 24 | PW | UC | 3-0 | 31-35-12 | D05763J | | 11 | | TB0133X | B086 | BJ | | 050-099, 155-199, 275-299 | |
| 503B | 24 | PW | UC | 4-0 | 31-35-12 | D05763J | | 11 | | TB0133X | D160 | BJ | | 150-154 | |
| 503R | 24 | PW | UC | 0-0 | 31-35-12 | D05763J | | 10 | | TB0133X | A086 | BJ | | 050-099, 155-199, 275-299 | |
| 503R | 24 | PW | UC | 0-0 | 31-35-12 | D05763J | | 10 | | TB0133X | C160 | BJ | | 150-154 | |
| 503Z | | | UC | 0-0 | 31-35-12 | D05763J | | 12 | | GDY0013 | S.. | 2 | | 050-099, 155-199, 275-299 | |
| 503Z | | | UC | 0-0 | 31-35-12 | D05763J | | 12 | | GDY0010 | S.. | 2 | | 150-154 | |
| 506B | 24 | PW | UF | 5-0 | 31-35-12 | D05763J | | 14 | | TB0133X | B038 | BJ | | ALL | |
| 506R | 24 | PW | UF | 0-0 | 31-35-12 | D05763J | | 13 | | TB0133X | A038 | BJ | | ALL | |
| 506Z | | | UF | 0-0 | 31-35-12 | D05763J | | 15 | | GDY0007 | S.. | 2 | | ALL | |
| 507B | 24 | PW | UG | 5-0 | 31-35-12 | D05763J | | 23 | | TB0133X | D038 | BJ | | ALL | |
| 507R | 24 | PW | UG | 0-0 | 31-35-12 | D05763J | | 22 | | TB0133X | C038 | BJ | | ALL | |
| 507Z | | | UG | 0-0 | 31-35-12 | D05763J | | 24 | | GDY0007 | S.. | 2 | | ALL | |
| 508 | 24 | PK | | 6-6 | 34-53-13 | D06119P | | 1 | | TB0133G | 114 | 2 | | ALL | |
| 509 | 24 | PK | | 6-6 | 34-53-13 | D06119P | | 2 | | TB0133G | 114 | 2 | | ALL | |
| 510 | 24 | PK | | 6-6 | 34-53-13 | D06119P | | 3 | | TB0133G | 115 | 2 | | ALL | |
| 511 | 24 | PK | | 6-6 | 34-53-13 | D06119P | | 4 | | TB0133G | 115 | 2 | | ALL | |
| 551B | 24 | PW | WA | 5-0 | 31-35-12 | D05763J | | 26 | | TB0133X | B039 | BJ | | ALL | |
| 551R | 24 | PW | WA | 0-0 | 31-35-12 | D05763J | | 25 | | TB0133X | A039 | BJ | | ALL | |
| 551Z | | | WA | 0-0 | 31-35-12 | D05763J | | 27 | | GDY0007 | S.. | 2 | | ALL | |
| 552B | 24 | PW | WB | 5-0 | 31-35-12 | D05763J | | 29 | | TB0133X | D039 | BJ | | ALL | |
| 552R | 24 | PW | WB | 0-0 | 31-35-12 | D05763J | | 28 | | TB0133X | C039 | BJ | | ALL | |
| 552Z | | | WB | 0-0 | 31-35-12 | D05763J | | 30 | | GDY0007 | S.. | 2 | | ALL | |
| 553B | 24 | PW | WC | 4-0 | 31-35-12 | D05763J | | 32 | | TB0133X | B141 | BJ | | 050-099, 155-199, 275-299 | |
| 553B | 24 | PW | WC | 4-0 | 31-35-12 | D05763J | | 32 | | TB0133X | B157 | BJ | | 150-154 | |
| 553R | 24 | PW | WC | 0-0 | 31-35-12 | D05763J | | 31 | | TB0133X | A141 | BJ | | 050-099, 155-199, 275-299 | |
| 553R | 24 | PW | WC | 0-0 | 31-35-12 | D05763J | | 31 | | TB0133X | A157 | BJ | | 150-154 | |
| 553Z | | | WC | 0-0 | 31-35-12 | D05763J | | 33 | | GDY0007 | S.. | 2 | | 050-099, 155-199, 275-299 | |
| 553Z | | | WC | 0-0 | 31-35-12 | D05763J | | 33 | | GDY0009 | S.. | 2 | | 150-154 | |
| 554B | 24 | PW | WD | 4-0 | 31-35-12 | D05763J | | 35 | | TB0133X | D141 | BJ | | 050-099, 155-199, 275-299 | |
| 554B | 24 | PW | WD | 4-0 | 31-35-12 | D05763J | | 35 | | TB0133X | D157 | BJ | | 150-154 | |
| 554R | 24 | PW | WD | 0-0 | 31-35-12 | D05763J | | 34 | | TB0133X | C141 | BJ | | 050-099, 155-199, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 44
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0143 | 286T0143 | | | E2-2 R,SHELF (continued) | | | | | | | | | | | |
| 554R | 24 | PW | WD | | 0-0 | 31-35-12 | D05763J | | 34 | | TB0133X | C157 | BJ | | 150-154 |
| 554Z | | | WD | | 0-0 | 31-35-12 | D05763J | | 36 | | GDY0007 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 554Z | | | WD | | 0-0 | 31-35-12 | D05763J | | 36 | | GDY0009 | S.. | 2 | | 150-154 |
| 555B | 24 | PW | WE | | 4-0 | 31-35-12 | D05763J | | 38 | | TB0133X | B142 | BJ | | 050-099, 155-199, 275-299 |
| 555B | 24 | PW | WE | | 4-0 | 31-35-12 | D05763J | | 38 | | TB0133X | B158 | BJ | | 150-154 |
| 555R | 24 | PW | WE | | 0-0 | 31-35-12 | D05763J | | 37 | | TB0133X | A142 | BJ | | 050-099, 155-199, 275-299 |
| 555R | 24 | PW | WE | | 0-0 | 31-35-12 | D05763J | | 37 | | TB0133X | A158 | BJ | | 150-154 |
| 555Z | | | WE | | 0-0 | 31-35-12 | D05763J | | 39 | | GDY0007 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 555Z | | | WE | | 0-0 | 31-35-12 | D05763J | | 39 | | GDY0009 | S.. | 2 | | 150-154 |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL | | | | | | | | | | | |
| 001 | 24 | PK | | | 4-0 | 34-12-12 | D04801J | | 8 | | D03942 | A2 | | | ALL |
| 002 | 24 | PK | | | 5-0 | 34-12-12 | D04801J | | 9 | | D03916 | A2 | | | ALL |
| 003 | 24 | PK | | | 4-0 | 34-12-12 | D04801J | | 10 | | D03948 | A2 | | | ALL |
| 004 | 16 | PA | | | 5-0 | 23-34-15 | D05191J | | 1 | | K00459 | B2 | C | | ALL |
| 005 | 16 | PA | | | 5-0 | 23-34-16 | D05191J | | 2 | | K00459 | D2 | C | | ALL |
| 006 | 12 | PA | | | 5-0 | 23-34-18 | D05191J | | 3 | | K00459 | A2 | C | | ALL |
| 007 | 12 | PA | | | 5-0 | 23-34-18 | D05191J | | 4 | | K00459 | C2 | C | | ALL |
| 008 | 12 | PA | | | 5-0 | 23-34-18 | D05191J | | 5 | | K00459 | A1 | C | | ALL |
| 009 | 16 | PA | | | 5-0 | 23-34-15 | D05191J | | 6 | | K00459 | B1 | C | | ALL |
| 010 | 16 | PA | | | 5-0 | 23-34-16 | D05191J | | 7 | | K00459 | D1 | C | | ALL |
| 011 | 12 | PA | | | 5-0 | 23-34-18 | D05191J | | 8 | | K00459 | C1 | C | | ALL |
| 012 | 22 | PA | | | 4-0 | 23-34-11 | D05193J | | 1 | | D01347 | A2 | | | 050-099 |
| 012 | 22 | PA | | | 3-6 | 23-34-11 | D05193J | | 1 | | D01347 | A2 | | | 150-199, 275-299 |
| 013 | 22 | PA | | | 4-0 | 23-34-11 | D05193J | | 2 | | TB0196Y | A002 | BJ | | 050-099 |
| 013 | 22 | PA | | | 3-6 | 23-34-11 | D05193J | | 2 | | TB0196Y | A002 | BJ | | 150-199, 275-299 |
| 014 | 22 | PA | | | 7-0 | 23-34-11 | D05193J | | 3 | | D01347 | X1 | | | 050-099 |
| 014 | 22 | PA | | | 3-6 | 23-34-11 | D05193J | | 3 | | D01347 | X1 | | | 150-199, 275-299 |
| 015 | 22 | PA | | | 5-0 | 23-34-11 | D05193J | | 4 | | TB0196Y | A011 | BJ | | 050-099 |
| 015 | 22 | PA | | | 3-6 | 23-34-11 | D05193J | | 4 | | TB0196Y | A011 | BJ | | 150-199, 275-299 |
| 016 | 22 | PA | | | 3-0 | 23-34-11 | K00459 | | X1 | C | TB0196Y | A011 | BJ | | ALL |
| 019 | 22 | PA | | | 4-0 | 30-31-11 | D05798J | | 8 | | D03948 | C1 | | | ALL |
| 01A | 24 | PV | AK | | 7-0 | 21-51-13 | D10128 | | 12 | | TB0196X | A016 | BJ | | ALL |
| 01AZ | | | AK | | 0-0 | 21-51-13 | D10128 | | DED | | TB0196X | DED | | | ALL |
| 01B | 24 | PV | AL | | 7-0 | 21-51-13 | D10128 | | 6 | | TB0196X | B016 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 45

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 01BZ | | | | AL | 0-0 | 21-51-13 | D10128 | | DED | | | | TB0196X | DED | | | ALL |
| 01C | 24 | | PV | AM | 7-0 | 21-51-13 | D10128 | | 2 | | | | TB0196X | C016 | BJ | | ALL |
| 01CZ | | | | AM | 0-0 | 21-51-13 | D10128 | | DED | | | | TB0196X | DED | | | ALL |
| 01D | 24 | | PV | AS | 6-0 | 21-51-13 | D10128 | | 4 | | | | TB0188X | A017 | BJ | | ALL |
| 01DZ | | | | AS | 0-0 | 21-51-13 | TB0188X | | DED | | | | D10128 | DED | | | ALL |
| 01E | 24 | | PV | AT | 6-0 | 21-51-13 | D10128 | | 8 | | | | TB0188X | B017 | BJ | | ALL |
| 01EZ | | | | AT | 0-0 | 21-51-13 | TB0188X | | DED | | | | D10128 | DED | | | ALL |
| 01F | 24 | | PV | AU | 6-0 | 21-51-13 | D10128 | | 1 | | | | TB0188X | C017 | BJ | | ALL |
| 01FZ | | | | AU | 0-0 | 21-51-13 | TB0188X | | DED | | | | D10128 | DED | | | ALL |
| 01G | 24 | | PK | | 3-0 | 36-11-51 | TB0188Y | | A001 | BJ | | | D05798J | 17 | | | ALL |
| 01H | 22 | | PA | | 3-0 | SPARE | D05798J | | 18 | | | | TB0186Y | A004 | BJ | | 150-154, 275 |
| 01J | 22 | | PA | | 3-0 | 36-11-51 | D05798J | | 19 | | | | TB0186Y | A004 | BJ | | ALL |
| 01K | 22 | | PA | | 4-0 | 36-11-51 | D05798J | | 22 | | | | TB0196D | C020 | 2 | | ALL |
| 01L | 22 | | PA | | 5-0 | 36-11-51 | D01722 | | X1 | | | | TB0186Y | A004 | BJ | | ALL |
| 01M | 22 | | PA | | 6-0 | 36-11-51 | D01722 | | X2 | | | | TB0196D | A020 | 2 | | ALL |
| 01N | 20 | | PA | | 3-0 | 36-11-51 | D01722 | | C2 | | | | GDX0005 | D.. | 2 | | ALL |
| 01P | 24 | | PK | | 5-0 | 36-11-41 | D01722 | | D2 | | | | TB0188X | D006 | BJ | | ALL |
| 01Q | 24 | | PK | | 4-0 | 36-11-41 | D01722 | | D1 | | | | D05798J | 24 | | | ALL |
| 01R | 24 | | PK | | 5-0 | 21-51-23 | D10132 | | 6 | | | | D05798J | 6 | | | ALL |
| 01S | 24 | | PK | | 5-0 | 21-51-23 | D10132 | | 2 | | | | D05798J | 21 | | | ALL |
| 01T | 24 | | PK | | 5-0 | 21-51-23 | D10132 | | 4 | | | | D05798J | 14 | | | ALL |
| 01U | 24 | | PK | | 5-0 | 21-51-23 | D10132 | | 8 | | | | D05798J | 15 | | | ALL |
| 01V | 24 | | PK | | 5-0 | 21-51-23 | D10132 | | 1 | | | | D05798J | 16 | | | ALL |
| 01W | 24 | | PK | | 5-0 | 21-51-23 | D10132 | | 12 | | | | D05798J | 7 | | | ALL |
| 01X | 20 | | PA | | 5-0 | 27-62-11 | D05664J | | 15 | | | | TB0200D | A017 | 2 | | ALL |
| 01Y | 22 | | PA | | 3-0 | 27-62-11 | D05664J | | 46 | | | | TB0186Z | 8 | BJ | | ALL |
| 020 | 24 | | PK | | 3-0 | 36-11-41 | D05798J | | 23 | | | | TB0188Y | A001 | BJ | | ALL |
| 021 | 24 | | PK | | 5-0 | 36-11-51 | D01722 | | C1 | | | | TB0188Y | A001 | BJ | | ALL |
| 022 | 22 | | PA | | 2-0 | 30-31-11 | D03948 | | B1 | | | | D03510 | D1 | | * | ALL |
| 024 | 22 | | PA | | 5-0 | 27-51-51 | D05662J | | 8 | | | | D02088 | A1 | | | 050-099 |
| 024 | 22 | | PA | | 3-6 | 27-51-51 | D05662J | | 8 | | | | D02088 | A1 | | | 150-199, 275-299 |
| 025 | 22 | | PA | | 5-0 | 27-51-51 | D05662J | | 9 | | | | D02088 | A3 | | | 050-099 |
| 025 | 22 | | PA | | 3-6 | 27-51-51 | D05662J | | 9 | | | | D02088 | A3 | | | 150-199, 275-299 |
| 026 | 24 | | PK | | 6-0 | 27-58-11 | D02272 | | 9 | | | | D05662J | 10 | | | 050-099 |
| 026 | 24 | | PK | | 5-0 | 27-58-11 | D02272 | | 9 | | | | D05662J | 10 | | | 150-199, 275-299 |
| 027 | 24 | | PK | | 6-0 | 27-58-11 | D02272 | | 14 | | | | D05662J | 11 | | | 050-099 |
| 027 | 24 | | PK | | 5-0 | 27-58-11 | D02272 | | 14 | | | | D05662J | 11 | | | 150-199, 275-299 |
| 028 | 24 | | PK | | 4-0 | 27-58-11 | D05662J | | 12 | | | | TB0200Z | 22 | BJ | | 050-099 |
| 028 | 24 | | PK | | 3-6 | 27-58-11 | D05662J | | 12 | | | | TB0200Z | 22 | BJ | | 150-199, 275-299 |

WIRE LIST D280T132

91-21-11
Section W0140
Page 46
Mar 14/2007

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 02A | 20 | | PA | 5-0 | 27-62-11 | D01804 | | A1 | | | | | TB0186Z | 8 | BJ | | ALL |
| 02B | 22 | | PA | 5-0 | 27-62-11 | D01804 | | B2 | | | | | TB0186Z | 8 | BJ | | ALL |
| 02C | 22 | | PA | 4-0 | 27-62-11 | D01804 | | X1 | | | | | TB0092Y | C001 | BJ | | ALL |
| 02D | 20 | | PA | 3-0 | 27-62-11 | D01804 | | A3 | | | | | GD0006 | D.. | 2 | | ALL |
| 02E | 22 | | PA | 2-0 | 27-62-11 | D01804 | | B3 | | | | | D01806 | B1 | | | ALL |
| 02F | 22 | | PA | 2-0 | 27-62-11 | D01804 | | B1 | | | | | D01806 | B3 | | | ALL |
| 02G | 20 | | PA | 3-0 | 27-62-11 | D01804 | | X2 | | | | | GD0006 | D.. | 2 | | ALL |
| 02I | 24 | | PK | 3-0 | 27-62-11 | TB0186Y | | C005 | BJ | | | | D05332J | 2 | | | ALL |
| 02K | 20 | | PA | 5-0 | 27-62-11 | D05664J | | 45 | | | | | D01804 | A2 | | | ALL |
| 02L | 20 | | PA | 5-0 | 27-62-11 | D05664J | | 44 | | | | | D01806 | A2 | | | ALL |
| 02M | 20 | | PA | 5-0 | 27-62-11 | TB0186Z | | 8 | BJ | | | | D01806 | A1 | | | ALL |
| 02N | 22 | | PA | 3-0 | 27-62-11 | D03980 | | 7 | | | | | D01806 | B2 | | | ALL |
| 02O | 20 | | PA | 3-0 | 27-62-11 | GD0006 | | D.. | 2 | | | | D01806 | A3 | | | ALL |
| 02P | 20 | | PA | 3-0 | 27-62-11 | GD0006 | | D.. | 2 | | | | D01806 | X2 | | | ALL |
| 02Q | 22 | | PA | 2-0 | 27-62-11 | D01806 | | X1 | | | | | D02418 | B1 | | | ALL |
| 02R | 22 | | PA | 6-0 | 27-62-11 | D03980 | | 4 | | | | | TB0186Y | A009 | BJ | | ALL |
| 02S | 20 | | PA | 2-0 | 27-62-11 | D03980 | | 2 | | | | | GD0006 | D.. | 2 | | ALL |
| 02T | 22 | | PA | 5-0 | 27-62-11 | D02420 | | D2 | | | | | TB0186Z | 8 | BJ | | ALL |
| 02U | 22 | | PA | 4-0 | 27-62-11 | D02420 | | B1 | | | | | TB0092Y | A004 | BJ | | ALL |
| 02V | 22 | | PA | 7-0 | 27-62-11 | D05664J | | 47 | | | | | TB0092Y | A004 | BJ | | ALL |
| 02W | 22 | | PA | 4-0 | 27-62-11 | D02420 | | X1 | | | | | TB0092Y | A004 | BJ | | ALL |
| 02X | 22 | | PA | 4-0 | 27-62-11 | D02420 | | D3 | | | | | TB0092Y | C001 | BJ | | ALL |
| 02Y | 22 | | PA | 2-0 | 27-62-11 | D02420 | | B2 | | | | | D02418 | B2 | | | ALL |
| 031 | 24 | | PK | 4-0 | 27-58-11 | D05664J | | 3 | | | | | TB0200Z | 22 | BJ | | ALL |
| 032 | 20 | | PA | 3-0 | 23-34-11 | K00459 | | X2 | C | | | | GD0010 | D.. | F | | ALL |
| 033 | 24 | | PK | 7-0 | 27-58-11 | D05664J | | 5 | | | | | TB0092Y | C009 | BJ | | ALL |
| 034 | 24 | | PK | 4-0 | 27-58-11 | D05664J | | 6 | | | | | TB0196Y | A012 | BJ | | ALL |
| 035 | 24 | | PK | 4-0 | 27-58-11 | D05664J | | 7 | | | | | TB0196Y | C011 | BJ | | ALL |
| 036 | 24 | | PK | 4-0 | 27-58-11 | D05664J | | 8 | | | | | TB0200Y | C023 | BJ | | ALL |
| 037 | 24 | | PK | 4-0 | 27-58-11 | D05664J | | 9 | | | | | TB0200Y | A024 | BJ | | ALL |
| 03A | 22 | | PA | 6-0 | 27-62-11 | D02420 | | A1 | | | | | TB0196Y | A001 | BJ | | ALL |
| 03B | 22 | | PA | 6-0 | 27-62-11 | D02420 | | X2 | | | | | TB0196X | A003 | BJ | | ALL |
| 03C | 20 | | PA | 3-0 | 27-62-11 | D02420 | | A2 | | | | | GD0006 | D.. | 2 | | ALL |
| 03D | 20 | | PA | 3-0 | 27-62-11 | D02420 | | C2 | | | | | GD0006 | D.. | 2 | | ALL |
| 03E | 22 | | PA | 1-0 | 27-62-11 | D02420 | | C3 | | | | | D02420 | B3 | | | ALL |
| 03F | 22 | | PA | 2-0 | 27-62-11 | D02420 | | C1 | | | | | D02418 | C1 | | | ALL |
| 03G | 22 | | PA | 1-0 | 27-62-11 | D02418 | | B3 | | | | | D02418 | C3 | | | ALL |
| 03I | 22 | | PA | 3-0 | 27-62-11 | D02418 | | C2 | | | | | D03980 | 3 | | | ALL |
| 03J | 22 | | PA | 4-0 | 27-62-11 | D02418 | | X1 | | | | | TB0092Y | A004 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 47

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | |
| 03K | 20 | PA | | | 4-0 | 27-62-11 | D02418 | | A2 | | GDX0006 | D.. | 2 | | ALL |
| 03L | 22 | PA | | | 4-0 | 27-62-11 | D02418 | | D3 | | TB0092Y | C001 | BJ | | ALL |
| 03M | 22 | PA | | | 4-0 | 27-62-11 | D02418 | | D2 | | TB0186Z | 8 | BJ | | ALL |
| 03N | 22 | PA | | | 7-0 | 27-62-11 | D05664J | | 48 | | TB0092Y | C001 | BJ | | ALL |
| 03P | 24 | PK | | | 3-0 | 29-11-22 | D05798J | | 36 | | TB0188Y | C012 | BJ | | ALL |
| 03Q | 22 | PA | | | 6-0 | 29-11-22 | D05798J | | 28 | | TB0092Y | C003 | BJ | | ALL |
| 03R | 24 | PK | | | 6-0 | 29-11-22 | D05798J | | 30 | | TB0092Z | 12 | BJ | | ALL |
| 03S | 22 | PA | | | 5-0 | 29-11-22 | D05798J | | 33 | | D00600 | C2 | | | ALL |
| 03T | 24 | PK | | | 4-0 | 29-11-22 | D00600 | | X1 | | TB0092Z | 12 | BJ | | ALL |
| 03U | 24 | PK | | | 4-0 | 29-11-22 | D00600 | | B2 | | TB0092Z | 12 | BJ | | ALL |
| 03V | 24 | PK | | | 5-0 | 29-11-22 | D00600 | | X2 | | TB0188X | D017 | BJ | | ALL |
| 03W | 24 | PK | | | 5-0 | 29-11-22 | D00600 | | A2 | | TB0188X | A018 | BJ | | ALL |
| 03X | 22 | PA | | | 4-0 | 29-11-22 | D00600 | | C1 | | TB0092Y | C003 | BJ | | ALL |
| 03Y | 24 | PK | | | 2-0 | 29-11-22 | D00600 | | A1 | | D00604 | A2 | | | ALL |
| 042 | 24 | PK | | | 5-0 | 23-34-12 | D05193J | | 8 | | D01881 | X2 | | | ALL |
| 043 | 24 | PK | | | 5-0 | 23-34-12 | D01881 | | A1 | | D05193J | 5 | | | 050-099 |
| 043 | 24 | PK | | | 5-0 | 23-34-12 | D05193J | | 6 | | D01881 | A1 | | | 150-199, 275-299 |
| 044 | 24 | PK | | | 5-0 | 23-34-12 | D01881 | | A2 | | D05193J | 7 | | | 050-099 |
| 044 | 24 | PK | | | 5-0 | 23-34-12 | D05193J | | 7 | | D01881 | A2 | | | 150-199, 275-299 |
| 045 | 24 | PK | | | 6-0 | 23-34-12 | D01881 | | X1 | | TB0196Y | A011 | BJ | | 050-099 |
| 045 | 24 | PK | | | 6-0 | 23-34-12 | TB0196Y | A011 | BJ | | D01881 | X1 | | | 150-199, 275-299 |
| 047 | 24 | PK | | | 5-0 | 27-51-51 | D05664J | | 30 | | D02088 | X2 | | | ALL |
| 048 | 24 | PK | | | 6-0 | 27-58-11 | D02272 | | 13 | | D05664J | 14 | | | ALL |
| 049 | 24 | PK | | | 6-0 | 27-58-11 | D05664J | | 17 | | D02272 | 12 | | | ALL |
| 04A | 24 | PK | | | 4-0 | 29-11-22 | D00600 | | B1 | | TB0092Y | C002 | BJ | | ALL |
| 04B | 22 | PA | | | 6-0 | 29-11-22 | D00600 | | C3 | | TB0196D | A024 | 2 | | ALL |
| 04C | 22 | PA | | | 3-0 | 29-11-22 | D05798J | | 34 | | TB0188Z | 13 | BJ | | ALL |
| 04D | 22 | PA | | | 5-0 | 29-11-22 | D00602 | | A2 | | TB0188Z | 13 | BJ | | ALL |
| 04E | 22 | PA | | | 4-0 | 29-11-22 | D00602 | | A1 | | TB0092Y | C003 | BJ | | ALL |
| 04F | 22 | PA | | | 7-0 | 29-11-22 | TB0188X | A021 | BJ | | TB0092Y | C003 | BJ | | ALL |
| 04G | 24 | PK | | | 4-0 | 29-11-22 | D00602 | | B2 | | TB0092Z | 12 | BJ | | ALL |
| 04H | 24 | PK | | | 4-0 | 29-11-22 | D00602 | | X1 | | TB0092Y | C002 | BJ | | ALL |
| 04I | 24 | PK | | | 2-0 | 29-11-22 | D00602 | | B3 | | D00604 | X1 | | | ALL |
| 04J | 24 | PK | | | 6-0 | 29-11-22 | D00602 | | X2 | | TB0196D | A023 | 2 | | ALL |
| 04K | 22 | PA | | | 5-0 | 29-11-22 | D00602 | | A3 | | TB0186X | C016 | BJ | | ALL |
| 04L | 22 | PQ | AY | | 3-0 | 29-11-22 | D05664J | | 42 | | TB0186Y | C018 | BJ | | ALL |
| 04LZ | | | AY | | 0-0 | 29-11-22 | D05664J | | DED | | TB0186Y | DED | | | ALL |
| 04M | 24 | PK | | | 4-0 | 29-11-22 | TB0092Y | | C002 | BJ | D00604 | B2 | | | ALL |
| 04N | 22 | PA | | | 3-0 | 29-11-22 | TB0196D | | C024 | 2 | TB0188Z | 13 | BJ | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 48
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | | |
| 04P | 24 | | PK | | 3-0 | 29-11-22 | TB0196D | | C021 | | 2 | | | TB0188Z | 13 | BJ | | ALL |
| 04R | 24 | | PK | | 3-0 | 29-11-22 | TB0186Y | | C018 | | BJ | | | TB0196D | C023 | 2 | | ALL |
| 04T | 24 | | PK | | 3-0 | 29-11-22 | TB0188Z | | | | 13 | BJ | | D05332J | 16 | | | ALL |
| 04U | 24 | | PK | | 3-0 | 29-11-22 | TB0186Y | | C018 | | BJ | | | D05332J | 15 | | | ALL |
| 04V | 24 | | PK | | 5-0 | 29-11-22 | D00604 | | | | B3 | | | TB0188Y | C012 | BJ | | ALL |
| 04W | 24 | | PK | | 5-0 | 29-11-22 | D00604 | | | | X2 | | | TB0188X | D018 | BJ | | ALL |
| 04X | 24 | | PK | | 4-0 | 29-11-22 | D00604 | | | | A3 | | | D05798J | 54 | | | ALL |
| 050 | 24 | | PK | | 6-0 | 27-58-11 | D05664J | | | | 16 | | | D03906 | 3 | | | ALL |
| 051 | 24 | | PK | | 6-0 | 27-58-11 | D02272 | | | | 3 | | | D05664J | 13 | | | ALL |
| 053 | 22 | | PA | | 4-0 | 76-11-11 | D05664J | | | | 39 | | | TB0196D | C022 | 2 | | ALL |
| 05A | 24 | | PK | | 3-0 | 29-11-22 | TB0188X | | A020 | | BJ | | | D05798J | 51 | | | ALL |
| 05B | 22 | | PA | | 3-0 | 29-11-22 | TB0188X | | B018 | | BJ | | | D05798J | 52 | | | ALL |
| 05C | 24 | | PK | | 3-0 | 29-11-22 | TB0188X | | A019 | | BJ | | | D05798J | 53 | | | ALL |
| 05D | 22 | | PA | | 3-0 | 29-11-22 | TB0188X | | B021 | | BJ | | | D05798J | 55 | | | ALL |
| 05E | 22 | | PA | | 3-0 | 27-09-13 | TB0188X | | C018 | | BJ | | | D04801J | 14 | | | ALL |
| 05F | 22 | | PA | | 3-0 | 27-09-13 | TB0188X | | B019 | | BJ | | | D04801J | 15 | | | ALL |
| 05G | 22 | | PQ | BA | 4-0 | 32-41-11 | TB0196D | | A021 | | 2 | | | D05798J | 35 | | | ALL |
| 05GZ | | | | BA | 0-0 | 32-41-11 | TB0196D | | | | DED | | | D05798J | DED | | | ALL |
| 05H | 24 | | PK | | 5-0 | 76-11-11 | D05332J | | | | 9 | | | TB0196D | C022 | 2 | | ALL |
| 05K | 24 | | PK | | 6-0 | 21-53-22 | D05798J | | | | 1 | | | TB0092Z | 6 | BJ | | ALL |
| 05L | 24 | | PK | | 6-0 | 21-53-22 | D05798J | | | | 37 | | | TB0092Z | 5 | BJ | | ALL |
| 05M | 24 | | PK | | 5-0 | 21-53-22 | D05798J | | | | 56 | | | D03662 | X2 | | | ALL |
| 05N | 24 | | PK | | 5-0 | 21-53-22 | D05798J | | | | 57 | | | D03654 | X2 | | | ALL |
| 05P | 24 | | PK | | 4-0 | 21-53-22 | TB0092Z | | | | 5 | BJ | | D03654 | X1 | | | ALL |
| 05Q | 24 | | PK | | 5-0 | 21-53-22 | D03654 | | A1 | | | | | TB0186X | C001 | BJ | | ALL |
| 05R | 24 | | PK | | 4-0 | 21-53-22 | D03654 | | A2 | | | | | TB0092Z | 6 | BJ | | ALL |
| 05S | 24 | | PK | | 4-0 | 21-53-22 | D03656 | | A2 | | | | | TB0092Z | 6 | BJ | | ALL |
| 05T | 24 | | PK | | 6-0 | 21-53-22 | D03656 | | A1 | | | | | TB0196X | D015 | BJ | | ALL |
| 05U | 24 | | PK | | 5-0 | 21-53-22 | D03656 | | | | X2 | | | D05798J | 58 | | | ALL |
| 05V | 24 | | PK | | 4-0 | 21-53-22 | D03656 | | | | X1 | | | TB0092Z | 5 | BJ | | ALL |
| 05W | 24 | | PK | | 4-0 | 21-53-22 | D03662 | | | | X1 | | | TB0092Z | 5 | BJ | | ALL |
| 05X | 24 | | PK | | 6-0 | 21-53-22 | D03662 | | A1 | | | | | TB0196X | A017 | BJ | | ALL |
| 05Y | 24 | | PK | | 4-0 | 21-53-22 | D03662 | | A2 | | | | | TB0092Z | 6 | BJ | | ALL |
| 064 | 20 | | PA | | 3-0 | 23-34-11 | D01347 | | | | X2 | | | GD0005 | D.. | 2 | | ALL |
| 067 | 24 | | PK | | 3-0 | 27-58-11 | D02272 | | | | 2 | | | TB0092Y | C010 | BJ | | ALL |
| 068 | 24 | | PK | | 3-0 | 27-58-11 | D02272 | | | | 4 | | | TB0092Y | A010 | BJ | | ALL |
| 069 | 24 | | PK | | 3-0 | 27-58-11 | D02272 | | | | 6 | | | TB0092Y | C009 | BJ | | ALL |
| 06A | 24 | | PK | | 4-0 | 21-53-22 | TB0092Z | | | | 5 | BJ | | D03658 | X1 | | | ALL |
| 06B | 24 | | PK | | 5-0 | 21-53-22 | D05798J | | | | 59 | | | D03658 | X2 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 49

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | |
| 06C | 24 | | PK | | 4-0 | 21-53-22 | TB0092Z | | 6 | BJ | D03658 | | A2 | | ALL |
| 06D | 24 | | PK | | 6-0 | 21-53-22 | TB0200X | | C004 | BJ | D03658 | | A1 | | ALL |
| 06E | 24 | | PK | | 4-0 | 21-53-22 | TB0092Z | | 6 | BJ | D03664 | | A2 | | ALL |
| 06F | 24 | | PK | | 4-0 | 21-53-22 | TB0092Z | | 6 | BJ | D03660 | | A2 | | ALL |
| 06G | 24 | | PK | | 4-0 | 21-53-22 | TB0092Z | | 5 | BJ | D03660 | | X1 | | ALL |
| 06H | 24 | | PK | | 5-0 | 21-53-22 | D05798J | | 60 | | D03660 | | X2 | | ALL |
| 06I | 24 | | PK | | 6-0 | 21-53-22 | TB0196X | | D016 | BJ | D03660 | | A1 | | ALL |
| 06J | 24 | | PK | | 5-0 | 21-53-22 | D05798J | | 61 | | D03664 | | X2 | | ALL |
| 06K | 24 | | PK | | 4-0 | 21-53-22 | TB0092Z | | 5 | BJ | D03664 | | X1 | | ALL |
| 06L | 24 | | PK | | 6-0 | 21-53-22 | TB0196X | | B017 | BJ | D03664 | | A1 | | ALL |
| 06M | 22 | | PA | | 5-0 | 27-62-11 | D05664J | | 22 | | TB0200R | A020 | 2 | | ALL |
| 06N | 20 | | PA | | 4-0 | 30-31-13 | D03952 | | X2 | | GD0007 | D.. | 2 | | ALL |
| 06P | 22 | | PA | | 7-1 | 27-62-11 | D23138 | | A2 | | TB0196Y | A001 | BJ | | ALL |
| 06Q | 22 | | PA | | 7-1 | 27-62-11 | D23138 | | A3 | | TB0186Y | C017 | BJ | | ALL |
| 070 | 24 | | PK | | 3-0 | 27-58-11 | D02272 | | 8 | | TB0092Y | C010 | BJ | | ALL |
| 071 | 24 | | PK | | 3-0 | 27-58-11 | D02272 | | 10 | | TB0092Y | A010 | BJ | | ALL |
| 074 | 24 | | PK | | 4-0 | 32-09-13 | D05664J | | 33 | | TB0196Z | 5 | BJ | | ALL |
| 076 | 24 | | PK | | 7-1 | 32-09-13 | D23138 | | C3 | | TB0188X | C007 | BJ | | ALL |
| 077 | 20 | | PA | | 3-0 | 32-09-13 | D01268 | | D2 | | GD0005 | D.. | 2 | | ALL |
| 07V | 22 | | PA | | 3-0 | 30-32-11 | D05798J | | 50 | | TB0196Y | A007 | BJ | | ALL |
| 083 | 24 | | PK | | 6-0 | 32-09-13 | D00542 | | X1 | | TB0196Z | 5 | BJ | | ALL |
| 084 | 24 | | PK | | 7-0 | 32-09-13 | D00542 | | X2 | | TB0188Y | C009 | BJ | | ALL |
| 085 | 24 | | PK | | 6-0 | 32-09-13 | D03510 | | X1 | | TB0196Z | 5 | BJ | | ALL |
| 086 | 24 | | PK | | 5-0 | 32-09-13 | D03510 | | X2 | | TB0188Y | C009 | BJ | | ALL |
| 087 | 22 | | PA | | 7-0 | 27-51-51 | TB0092Y | | A001 | BJ | D05664J | 10 | | | ALL |
| 092 | 22 | | PA | | 4-0 | 27-51-51 | D02088 | | A2 | | TB0092Y | A001 | BJ | | ALL |
| 093 | 22 | | PA | | 4-0 | 27-51-51 | D02088 | | X1 | | TB0092Y | A001 | BJ | | ALL |
| 094 | 24 | | PK | | 3-0 | 27-58-11 | D03906 | | 8 | | TB0268X | C001 | BJ | | ALL |
| 095 | 24 | | PK | | 3-0 | 27-58-11 | D03906 | | 2 | | TB0092Y | C010 | BJ | | ALL |
| 096 | 24 | | PK | | 3-0 | 27-58-11 | D03906 | | 5 | | TB0268X | B001 | BJ | | ALL |
| 097 | 24 | | PK | | 3-0 | 27-58-11 | D03906 | | 4 | | TB0268X | D001 | BJ | | ALL |
| 098 | 24 | | PK | | 3-0 | 27-58-11 | D03906 | | 6 | | TB0092Y | A010 | BJ | | ALL |
| 099 | 24 | | PK | | 3-0 | 27-58-11 | D03906 | | 7 | | TB0092Y | C009 | BJ | | ALL |
| 100 | 24 | | PK | | 3-0 | 27-58-11 | D03906 | | 1 | | TB0268X | A001 | BJ | | ALL |
| 101 | 20 | | PA | | 6-0 | 30-71-21 | TB0268G | | 7 | 2 | TB0196G | 10 | 2 | | 050-099 |
| 101 | 20 | | PA | | 7-0 | 30-71-21 | TB0268G | | 7 | 2 | TB0196G | 10 | 2 | | 150-199 |
| 101 | 22 | | PA | | 7-0 | 30-71-21 | TB0268G | | 7 | 2 | TB0186Y | C011 | BJ | | 275-299 |
| 102 | 20 | | PA | | 3-0 | 30-71-21 | D11814 | | A2 | | TB0268G | 7 | 2 | | 050-099 |
| 102 | 22 | | PA | | 3-0 | 30-71-21 | TB0268G | | 7 | 2 | D11814 | A2 | | | 150-154, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 50
Mar 14/2007

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 102 | 20 | | PA | 3-0 | 30-71-21 | TB0268G | | 7 | 2 | | | | D11814 | A2 | | | 155-199 |
| 103 | 20 | | PA | 3-0 | 30-71-21 | D11814 | | X1 | | | | | TB0268G | 7 | 2 | | 050-099 |
| 103 | 22 | | PA | 3-0 | 30-71-21 | TB0268G | | 7 | 2 | | | | D11814 | X1 | | | 150-154, 275-299 |
| 103 | 20 | | PA | 3-0 | 30-71-21 | TB0268G | | 7 | 2 | | | | D11814 | X1 | | | 155-199 |
| 104 | 20 | | PA | 5-0 | 30-71-21 | D11814 | | A1 | | | | | TB0186Y | A020 | BJ | | 050-099 |
| 104 | 22 | | PA | 5-0 | 30-71-21 | TB0186Y | | A012 | BJ | | | | D11814 | A1 | | | 150-154, 275-299 |
| 104 | 20 | | PA | 5-0 | 30-71-21 | TB0186Y | | A012 | BJ | | | | D11814 | A1 | | | 155-199 |
| 105 | 20 | | PA | 5-0 | 30-71-21 | D11814 | | X2 | | | | | TB0186Y | C012 | BJ | | 050-099 |
| 105 | 22 | | PA | 5-0 | 30-71-21 | TB0186Y | | C012 | BJ | | | | D11814 | X2 | | | 150-154, 275-299 |
| 105 | 20 | | PA | 5-0 | 30-71-21 | TB0186Y | | C012 | BJ | | | | D11814 | X2 | | | 155-199 |
| 106 | 20 | | PA | 3-0 | 30-71-21 | D11814 | | B2 | | | | | TB0268G | 7 | 2 | | 050-099 |
| 107 | 20 | | PA | 5-0 | 30-71-21 | D11814 | | B1 | | | | | TB0186Y | A012 | BJ | | 050-099 |
| 10F | 20 | | PA | 5-6 | 27-58-11 | D05662J | | 23 | | | | | GDX0005 | A.. | 2 | | 156-157, 166-199, 277-299 |
| 10H | 20 | | PA | 6-0 | 27-58-11 | D05664J | | 52 | | | | | GDX0005 | A.. | 2 | | 156-157, 166-199, 277-299 |
| 114 | 20 | | PA | 3-0 | 30-31-13 | D10186 | | B2 | | | | | GDX0005 | A.. | 2 | | ALL |
| 115 | 22 | | PA | 5-0 | 30-31-13 | D10186 | | B1 | | | | | TB0186X | D002 | BJ | | ALL |
| 116 | 22 | | PA | 4-0 | 30-31-13 | D05798J | | 20 | | | | | D00542 | A3 | | | ALL |
| 118 | 22 | | PA | 2-0 | 30-31-13 | D00542 | | D1 | | * | | | D03952 | B1 | | | ALL |
| 119 | 24 | | PV | 2-0 | 30-31-13 | D00542 | | B2 | | | | | D03952 | D3 | | | ALL |
| 119Z | | | S | 0-0 | 30-31-13 | D00542 | | DED | | | | | D03952 | DED | | | ALL |
| 11B | 22 | | PA | 6-0 | 32-45-11 | D13530 | | A3 | | | | | D05664J | 2 | | | 050-099 |
| 11B | 22 | | PA | 7-0 | 32-45-11 | D13530 | | A3 | | | | | D05664J | 2 | | | 150-199, 275-299 |
| 11C | 22 | | PA | 6-0 | 32-45-11 | D13530 | | A2 | | | | | D05664J | 19 | | | 050-099 |
| 11C | 22 | | PA | 7-0 | 32-45-11 | D13530 | | A2 | | | | | D05664J | 19 | | | 150-199, 275-299 |
| 11D | 22 | | PA | 5-0 | 32-45-11 | D13530 | | A1 | | | | | TB0188Y | C003 | BJ | | 050-099 |
| 11D | 22 | | PA | 7-0 | 32-45-11 | D13530 | | A1 | | | | | TB0188Y | C003 | BJ | | 150-199 |
| 11D | 22 | | PA | 7-0 | 32-45-11 | D13530 | | A1 | | | | | TB0188Y | A008 | BJ | | 275-299 |
| 11E | 22 | | PA | 5-0 | 32-45-11 | D13530 | | X1 | | | | | TB0188Y | C003 | BJ | | 050-099 |
| 11E | 22 | | PA | 7-0 | 32-45-11 | TB0188Y | | C003 | BJ | | | | D13530 | X1 | | | 150-199 |
| 11E | 22 | | PA | 7-0 | 32-45-11 | D13530 | | X1 | | | | | TB0188Y | A008 | BJ | | 275-299 |
| 11F | 20 | | PA | 3-0 | 32-45-11 | D13530 | | X2 | | | | | GDX0005 | D.. | 2 | | 050-099 |
| 11F | 20 | | PA | 10-0 | 32-45-11 | D13530 | | X2 | | | | | GDX0005 | D.. | 2 | | 150-199, 275-299 |
| 120 | 24 | | PK | 5-0 | 30-31-13 | D03952 | | X1 | | | | | TB0092Y | C007 | BJ | | ALL |
| 121 | 22 | | PQ | 4-0 | 30-31-13 | D03952 | | D2 | | | | | TB0186Y | C014 | BJ | | ALL |
| 121Z | | | T | 0-0 | 30-31-13 | D03952 | | DED | | | | | TB0186Y | DED | | | ALL |
| 122 | 22 | | PA | 5-0 | 30-31-13 | D00542 | | A1 | | | | | TB0186X | D016 | BJ | | ALL |
| 123 | 24 | | PV | 5-0 | 30-31-13 | D00542 | | B3 | | | | | TB0186X | B016 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 51

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 123Z | | | | AV | 0-0 | 30-31-13 | D00542 | | DED | | | | TB0186X | DED | | | ALL |
| 124 | 22 | | PA | | 4-0 | 30-31-13 | D03952 | | C1 | | | | D05664J | 41 | | | ALL |
| 125 | 20 | | PQ | BC | 4-0 | 30-31-13 | D03952 | | B2 | | | | GDX0005 | D.. | 2 | | ALL |
| 125Z | | | | BC | 0-0 | 30-31-13 | D03952 | | DED | | | | GDX0005 | DED | | | ALL |
| 127 | 20 | | PA | | 4-0 | 30-31-13 | D03952 | | D1 | | | | GDX0006 | S.. | 2 | | ALL |
| 128 | 22 | | PQ | AW | 6-0 | 30-31-23 | D00542 | | C1 | | | | TB0196X | C003 | BJ | | ALL |
| 128Z | | | | AW | 0-0 | 30-31-23 | D00542 | | DED | | | | TB0196X | DED | | | ALL |
| 129 | 22 | | PQ | AX | 6-0 | 30-31-23 | D00542 | | C2 | | | | TB0196X | D003 | BJ | | ALL |
| 129Z | | | | AX | 0-0 | 30-31-23 | D00542 | | DED | | | | TB0196X | DED | | | ALL |
| 130 | 24 | | PK | | 6-0 | 30-31-23 | D10188 | | C2 | | | | TB0196X | C014 | BJ | | ALL |
| 131 | 24 | | PK | | 5-0 | 30-31-23 | D10188 | | C3 | | | | D05332J | 6 | | | ALL |
| 132 | 22 | | PA | | 3-0 | 30-31-23 | D05798J | | 11 | | | | TB0188Y | A012 | BJ | | ALL |
| 133 | 24 | | PK | | 3-0 | 30-31-23 | D05332J | | 5 | | | | TB0188Y | A012 | BJ | | ALL |
| 134 | 22 | | PA | | 4-0 | 30-32-21 | D05798J | | 31 | | | | TB0196Y | C012 | BJ | | ALL |
| 135 | 24 | | PK | | 4-0 | 30-32-21 | D05332J | | 7 | | | | TB0196Y | C012 | BJ | | ALL |
| 138 | 22 | | PA | | 2-0 | 23-34-11 | TB0196Y | | A011 | BJ | | | TB0196D | C025 | 2 | | ALL |
| 139 | 22 | | PA | | 3-0 | 23-34-11 | K00459 | | X2 | C | | | TB0196D | A025 | 2 | | ALL |
| 144 | 24 | | PK | | 7-0 | 27-58-11 | D02272 | | 11 | | | | TB0200Y | C023 | BJ | | ALL |
| 145 | 24 | | PK | | 7-0 | 27-58-11 | D02272 | | 7 | | | | TB0200Y | A024 | BJ | | ALL |
| 146 | 24 | | PK | | 7-0 | 27-58-11 | D02272 | | 1 | | | | TB0196Y | C011 | BJ | | ALL |
| 147 | 24 | | PK | | 7-0 | 27-58-11 | D02272 | | 5 | | | | TB0196Y | A012 | BJ | | ALL |
| 148 | 24 | | PK | | 4-0 | 31-31-13 | D04801J | | 18 | | | | TB0200Z | 22 | BJ | | ALL |
| 151 | 24 | | PK | | 4-0 | 73-21-12 | D05664J | | 28 | | | | D03924 | A2 | | | 050-099 |
| 151 | 24 | | PK | | 5-0 | 73-21-12 | D03924 | | A2 | | | | D05664J | 28 | | | 150-199 |
| 151 | 24 | | PK | | 5-0 | 73-21-12 | D05664J | | 28 | | | | D03924 | A2 | | | 275-299 |
| 152 | 24 | | PK | | 2-0 | 22-41-11 | D05662J | | 1 | | | | D04801J | 22 | | | 050-099 |
| 152 | 24 | | PK | | 1-6 | 22-41-11 | D05662J | | 1 | | | | D04801J | 22 | | | 150-199, 275-299 |
| 178 | 22 | | PA | | 7-0 | 23-34-11 | D01347 | | A1 | | | | TB0196Y | A002 | BJ | | 050-099 |
| 178 | 22 | | PA | | 4-0 | 23-34-11 | D01347 | | A1 | | | | TB0196Y | A002 | BJ | | 150-199, 275-299 |
| 18B | 24 | | PK | | 3-0 | 22-32-13 | TB0188X | | B022 | BJ | | | D04801J | 7 | | | 050-099 |
| 18B | 24 | | PK | | 4-0 | 22-32-13 | TB0188X | | B022 | BJ | | | D04801J | 7 | | | 150-199, 275-299 |
| 18G | 24 | | PV | HS | 4-0 | 73-21-14 | D05664J | | 31 | | | | TB0200Y | A005 | BJ | | ALL |
| 18GZ | | | | HS | 0-0 | 73-21-14 | D05664J | | 32 | | | | TB0200Y | C006 | BJ | | ALL |
| 201B | 24 | | PL | C | 4-0 | 31-31-13 | D04801J | | 20 | | | | TB0200Y | A024 | BJ | | ALL |
| 201R | 24 | | PL | C | 0-0 | 31-31-13 | D04801J | | 19 | | | | TB0200Y | C023 | BJ | | ALL |
| 202B | 24 | | PL | D | 4-0 | 31-31-13 | D04801J | | 6 | | | | TB0196Y | C011 | BJ | | ALL |
| 202R | 24 | | PL | D | 0-0 | 31-31-13 | D04801J | | 5 | | | | TB0196Y | A012 | BJ | | ALL |
| 203B | 22 | | PR | AN | 7-0 | 21-51-22 | D10132 | | 14 | | | | TB0196X | D017 | BJ | | ALL |
| 203R | 22 | | PR | AN | 0-0 | 21-51-22 | D10132 | | 3 | | | | TB0196X | C017 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 52

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 203Z | | | | AN | 0-0 | 21-51-22 | D10132 | | DED | | | | TB0196X | DED | | | ALL |
| 204B | 22 | PR | | AP | 7-0 | 21-51-22 | D10132 | | 7 | | | | TB0196X | B018 | BJ | | ALL |
| 204R | 22 | PR | | AP | 0-0 | 21-51-22 | D10132 | | 5 | | | | TB0196X | A018 | BJ | | ALL |
| 204Z | | | | AP | 0-0 | 21-51-22 | D10132 | | DED | | | | TB0196X | DED | | | ALL |
| 205B | 22 | PB | | AQ | 6-0 | 21-51-12 | D10128 | | 14 | | | | D05798J | 39 | | | ALL |
| 205R | 22 | PB | | AQ | 0-0 | 21-51-12 | D10128 | | 3 | | | | D05798J | 38 | | | ALL |
| 206B | 22 | PB | | AR | 6-0 | 21-51-12 | D10128 | | 7 | | | | D05798J | 40 | | | ALL |
| 206R | 22 | PB | | AR | 0-0 | 21-51-12 | D10128 | | 5 | | | | D05798J | 41 | | | ALL |
| 20B | 22 | PA | | | 8-0 | 30-81-11 | D05664J | | 24 | | | | TB0266D | C008 | 2 | | 050-099 |
| 20B | 22 | PA | | | 9-0 | 30-81-11 | D05664J | | 24 | | | | TB0266D | C008 | 2 | | 150-199 |
| 20C | 22 | PA | | | 2-0 | 30-81-11 | TB0266D | | C002 | 2 | | | TB0266D | C008 | 2 | | 050-099 |
| 20C | 22 | PA | | | 1-0 | 30-81-11 | TB0266D | | C002 | 2 | | | TB0266D | C008 | 2 | | 150-199 |
| 20D | 22 | PA | | | 8-0 | 30-81-11 | D05664J | | 26 | | | | TB0266D | C007 | 2 | | 050-099 |
| 20D | 22 | PA | | | 9-0 | 30-81-11 | D05664J | | 26 | | | | TB0266D | C007 | 2 | | 150-199 |
| 20E | 22 | PA | | | 4-0 | 30-81-11 | D12148 | | 8 | | | | TB0266X | B010 | BJ | | 050-099, 150-199 |
| 20F | 22 | PA | | | 4-0 | 30-81-11 | D12148 | | 5 | | | | TB0266X | A010 | BJ | | 050-099, 150-199 |
| 20G | 22 | PA | | | 4-0 | 30-81-11 | D12144 | | 6 | | | | TB0266Z | 11 | BJ | | 050-099, 150-199 |
| 20H | 22 | PA | | | 4-0 | 30-81-11 | D12144 | | 2 | | | | TB0266Z | 11 | BJ | | 050-099, 150-199 |
| 20J | 22 | PA | | | 9-0 | 30-81-11 | D12144 | | 7 | | | | D05664J | 43 | | | 050-099, 150-199 |
| 20K | 22 | PA | | | 4-0 | 30-81-11 | D12144 | | 3 | | | | TB0266Y | A019 | BJ | | 050-099 |
| 20K | 22 | PA | | | 12-0 | 30-81-11 | D12144 | | 3 | | | | TB0266Y | A019 | BJ | | 150-199 |
| 20L | 22 | PA | | | 8-0 | 30-81-11 | D05664J | | 38 | | | | TB0266Y | A016 | BJ | | 050-099 |
| 20L | 22 | PA | | | 9-0 | 30-81-11 | D05664J | | 38 | | | | TB0266Y | A016 | BJ | | 150-199 |
| 20M | 22 | PA | | | 4-0 | 30-81-11 | D12148 | | 6 | | | | TB0266X | D010 | BJ | | 050-099, 150-199 |
| 20P | 22 | PA | | | 4-0 | 30-81-11 | D12148 | | 2 | | | | TB0266X | C010 | BJ | | 050-099, 150-199 |
| 20R | 22 | PA | | | 4-0 | 30-81-11 | D12148 | | 7 | | | | TB0266Y | A016 | BJ | | 050-099, 150-199 |
| 20S | 22 | PA | | | 4-0 | 30-81-11 | D12148 | | 3 | | | | TB0266Y | C016 | BJ | | 050-099, 150-199 |
| 20T | 22 | PA | | | 11-0 | 30-81-11 | D12144 | | 1 | | | | TB0092Y | A009 | BJ | | 050-099 |
| 20T | 22 | PA | | | 12-0 | 30-81-11 | D12144 | | 1 | | | | TB0092Y | A009 | BJ | | 150-199 |
| 20U | 22 | PA | | | 12-0 | 30-81-11 | D12144 | | 5 | | | | TB0268D | C011 | 2 | | 050-099, 150-199 |
| 20V | 22 | PA | | | 6-0 | 30-81-11 | D05332J | | 18 | | | | TB0092Y | A009 | BJ | | 050-099 |
| 20V | 22 | PA | | | 9-0 | 30-81-11 | TB0092Y | | A009 | BJ | | | D05332J | 18 | | | 150-199 |
| 20W | 22 | PA | | | 8-0 | 30-81-11 | D05332J | | 19 | | | | TB0266Y | A016 | BJ | | 050-099 |
| 20W | 22 | PA | | | 9-0 | 30-81-11 | TB0266Y | | A016 | BJ | | | D05332J | 19 | | | 150-199 |
| 20X | 22 | PA | | | 3-0 | 30-81-11 | TB0268D | | A011 | 2 | | | TB0092Y | A007 | BJ | | 050-099, 150-199 |
| 21A | 20 | PA | | | 8-0 | 30-21-11 | D05193J | | 9 | | | | TB0266D | A013 | 2 | | 050-099 |
| 21A | 20 | PA | | | 9-0 | 30-21-11 | D05193J | | 5 | | | | TB0266D | A013 | 2 | | 150-154 |
| 21A | 20 | PA | | | 9-0 | 30-21-11 | D05193J | | 9 | | | | TB0266D | A013 | 2 | | 155-199 |
| 224 | 24 | PK | | | 9-2 | 32-09-13 | D23138 | | C2 | | | | D01268 | D1 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 53

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | | |
| 224 | 24 | | PK | | 8-2 | 32-09-13 | D23138 | | C2 | | | | D01268 | | D1 | | | 275-299 |
| 22A | 20 | | PA | | 2-0 | 30-21-11 | TB0266D | | C013 | 2 | | | TB0266D | | C007 | 2 | | 050-099 |
| 22A | 20 | | PA | | 1-0 | 30-21-11 | TB0266D | | C013 | 2 | | | TB0266D | | C007 | 2 | | 150-199 |
| 50A | 22 | | PA | | 2-0 | 30-81-11 | TB0266D | | C002 | 2 | | | TB0266R | | A017 | 2 | | 050-099 |
| 50A | 22 | | PA | | 1-0 | 30-81-11 | TB0266D | | C002 | 2 | | | TB0266R | | A017 | 2 | | 150-199 |
| 521 | 22 | | PA | | 6-0 | 30-32-11 | D10186 | | C2 | | | | TB0196Y | | C007 | BJ | | ALL |
| 522 | 22 | | PA | | 6-0 | 30-32-11 | D10186 | | C1 | | | | TB0196Y | | A007 | BJ | | ALL |
| 534 | 22 | | PA | | 4-0 | 30-32-11 | D05798J | | 29 | | | | TB0196Y | | C007 | BJ | | ALL |
| 536 | 24 | | PK | | 4-0 | 30-32-11 | D03916 | | X1 | | | | TB0092Y | | C007 | BJ | | ALL |
| 538 | 22 | | PQ | AA | 5-0 | 30-32-11 | D03916 | | D2 | | | | TB0200Y | | A006 | BJ | | ALL |
| 538Z | | | | AA | 0-0 | 30-32-11 | D03916 | | DED | | | | TB0200Y | | DED | | | ALL |
| 539 | 22 | | PA | | 4-0 | 30-32-11 | D03916 | | C1 | | | | D05662J | | 2 | | | 050-099 |
| 539 | 22 | | PA | | 3-6 | 30-32-11 | D03916 | | C1 | | | | D05662J | | 2 | | | 150-199, 275-299 |
| 540 | 20 | | PA | | 4-0 | 30-32-11 | D03916 | | B1 | | | | GD0007 | | A.. | 2 | | ALL |
| 541 | 20 | | PA | | 4-0 | 30-32-11 | D03916 | | X2 | | | | GD0007 | | D.. | 2 | | ALL |
| 542 | 20 | | PA | | 4-0 | 34-12-12 | D03916 | | C3 | | | | GD0007 | | D.. | 2 | | ALL |
| 543 | 20 | | PQ | AB | 4-0 | 30-32-11 | D03916 | | B2 | | | | GD0007 | | D.. | 2 | | ALL |
| 543Z | | | | AB | 0-0 | 30-32-11 | D03916 | | DED | | | | GD0007 | | DED | | | ALL |
| 550 | 22 | | PQ | AC | 3-0 | 30-33-11 | D10186 | | D1 | | | | D03942 | | D3 | | | ALL |
| 550Z | | | | AC | 0-0 | 30-33-11 | D10186 | | DED | | | | D03942 | | DED | | | ALL |
| 555 | 22 | | PQ | AD | 4-0 | 30-33-11 | D03942 | | D2 | | | | TB0188Y | | A009 | BJ | | ALL |
| 555Z | | | | AD | 0-0 | 30-33-11 | D03942 | | DED | | | | TB0188Y | | DED | | | ALL |
| 556 | 22 | | PA | | 5-0 | 30-33-11 | D03942 | | C1 | | | | TB0196X | | B015 | BJ | | ALL |
| 559 | 22 | | PQ | AF | 7-0 | 30-33-11 | D10186 | | D2 | | | | TB0196X | | C015 | BJ | | ALL |
| 559Z | | | | AF | 0-0 | 30-33-11 | D10186 | | DED | | | | TB0196X | | DED | | | ALL |
| 561 | 20 | | PA | | 4-0 | 30-33-11 | D03942 | | X2 | | | | GD0007 | | D.. | 2 | | ALL |
| 562 | 24 | | PK | | 5-0 | 30-33-11 | D03942 | | X1 | | | | TB0092Z | | 11 | BJ | | ALL |
| 563 | 22 | | PQ | AE | 5-0 | 30-33-11 | D10186 | | D3 | | | | TB0188Y | | A009 | BJ | | ALL |
| 563Z | | | | AE | 0-0 | 30-33-11 | D10186 | | DED | | | | TB0188Y | | DED | | | ALL |
| 564 | 20 | | PA | | 4-0 | 30-33-11 | D03942 | | B1 | | | | GD0007 | | A.. | 2 | | ALL |
| 565 | 22 | | PA | | 4-0 | 30-33-11 | TB0196X | | A015 | BJ | | | D05798J | | 32 | | | ALL |
| 566 | 20 | | PA | | 4-0 | 34-12-12 | D03942 | | C3 | | | | GD0007 | | D.. | 2 | | ALL |
| 567 | 20 | | PQ | AH | 4-0 | 30-33-11 | D03942 | | B2 | | | | GD0007 | | D.. | 2 | | ALL |
| 567Z | | | | AH | 0-0 | 30-33-11 | D03942 | | DED | | | | GD0007 | | DED | | | ALL |
| 5AC | 22 | | PQ | XX | 6-3 | 30-34-11 | D01268 | | C2 | | | | TB0186Y | | C009 | BJ | | ALL |
| 5ACZ | | | | XX | 0-0 | 30-34-11 | D01268 | | DED | | | | TB0186Y | | DED | | | ALL |
| 5AD | 22 | | PQ | XY | 6-3 | 30-34-11 | D01268 | | C3 | | | | TB0186Y | | A010 | BJ | | ALL |
| 5ADZ | | | | XY | 0-0 | 30-34-11 | D01268 | | DED | | | | TB0186Y | | DED | | | ALL |
| 600 | 22 | | PA | | 3-0 | 30-34-11 | D05798J | | 4 | | | | TB0186Y | | C009 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0140
Page 54
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | | |
| 604 | 22 | | PA | | 3-0 | 30-34-11 | D03924 | | | | C1 | | | TB0186Y | A010 | BJ | | ALL |
| 605 | 20 | | PA | | 4-0 | 30-34-11 | D03924 | | | | X2 | | | GDX0005 | D.. | 2 | | ALL |
| 606 | 24 | | PK | | 2-0 | 30-34-11 | TB0092Y | | | A008 | BJ | | | TB0092Z | 11 | BJ | | ALL |
| 609 | 22 | | PQ | BG | 4-0 | 30-34-11 | D03924 | | | | B1 | | | TB0188X | C020 | BJ | | 050-099 |
| 609 | 22 | | PA | | 5-0 | 30-34-11 | D03924 | | | | B1 | | | TB0188X | C020 | BJ | | 150-199, 275-299 |
| 609Z | | | | BG | 0-0 | 30-34-11 | D03924 | | | | DED | | | TB0188X | DED | | | 050-099 |
| 60A | 22 | | PA | | 10-0 | 30-81-11 | D05664J | | | | 40 | | | TB0266Z | 12 | BJ | | 050-099, 150-199 |
| 615 | 24 | | PK | | 5-0 | 32-09-13 | D01268 | | | | X1 | | | TB0196Z | 5 | BJ | | ALL |
| 616 | 24 | | PK | | 5-0 | 32-09-13 | D01268 | | | | X2 | | | D05664J | 27 | | | ALL |
| 623 | 22 | | PA | | 7-0 | 27-62-11 | D05664J | | | | 23 | | | TB0092Y | A002 | BJ | | ALL |
| 624 | 22 | | PA | | 4-0 | 27-62-11 | D02418 | | | | A1 | | | TB0092Y | A002 | BJ | | ALL |
| 625 | 22 | | PA | | 2-0 | 27-62-11 | D01268 | | | | B1 | | | D02418 | X2 | | | ALL |
| 626 | 22 | | PA | | 4-0 | 27-62-11 | D01268 | | | | B2 | | | TB0092Y | A002 | BJ | | ALL |
| 628 | 22 | | PA | | 11-8 | 27-62-11 | D05662J | | | | 3 | | | TB0186Y | C017 | BJ | | 050-099, 150-199 |
| 628 | 22 | | PA | | 3-6 | 27-62-11 | D05662J | | | | 3 | | | TB0186Y | C017 | BJ | | 275-299 |
| 638 | 22 | | PA | | 5-0 | 30-34-11 | D10230 | | | | A2 | | | TB0186Y | C009 | BJ | | ALL |
| 640 | 22 | | PA | | 5-0 | 30-34-11 | D10230 | | | | A1 | | | TB0186Y | A010 | BJ | | ALL |
| 647 | 22 | | PQ | BL | 7-0 | 28-22-31 | D05664J | | | | 53 | | | TB0268Y | A005 | BJ | | ALL |
| 647Z | | | | BL | 0-0 | 28-22-31 | D05664J | | | | DED | | | TB0268Y | DED | | | ALL |
| 648 | 22 | | PQ | CL | 7-0 | 28-22-31 | D05664J | | | | 29 | | | TB0268Y | C009 | BJ | | ALL |
| 648Z | | | | CL | 0-0 | 28-22-31 | D05664J | | | | DED | | | TB0268Y | DED | | | ALL |
| 649 | 22 | | PQ | DL | 9-0 | 28-22-31 | D05664J | | | | 54 | | | D02987 | 14 | | | ALL |
| 649Z | | | | DL | 0-0 | 28-22-31 | D05664J | | | | DED | | | D02987 | DED | | | ALL |
| 651 | 22 | | PQ | EL | 4-0 | 28-22-31 | TB0092Y | | | A003 | BJ | | | TB0268X | C002 | BJ | | ALL |
| 651Z | | | | EL | 0-0 | 28-22-31 | TB0092Y | | | | DED | | | TB0268X | DED | | | ALL |
| 652 | 20 | | PQ | FL | 11-0 | 28-22-31 | D02987 | | | | 3 | | | GDX0007 | D.. | 2 | | ALL |
| 652Z | | | | FL | 0-0 | 28-22-31 | D02987 | | | | DED | | | GDX0007 | DED | | | ALL |
| 653 | 22 | | PQ | GL | 7-0 | 28-22-31 | D05664J | | | | 55 | | | TB0092Y | A003 | BJ | | ALL |
| 653Z | | | | GL | 0-0 | 28-22-31 | D05664J | | | | DED | | | TB0092Y | DED | | | ALL |
| 654 | 22 | | PQ | HL | 12-0 | 28-22-31 | D02987 | | | | 13 | | | TB0092Y | A003 | BJ | | ALL |
| 654Z | | | | HL | 0-0 | 28-22-31 | D02987 | | | | DED | | | TB0092Y | DED | | | ALL |
| 655 | 22 | | PQ | IL | 12-0 | 28-22-31 | D02987 | | | | 7 | | | TB0268Y | A005 | BJ | | ALL |
| 655Z | | | | IL | 0-0 | 28-22-31 | D02987 | | | | DED | | | TB0268Y | DED | | | ALL |
| 656 | 22 | | PQ | JL | 12-0 | 28-22-31 | D02987 | | | | 5 | | | TB0268Y | C009 | BJ | | ALL |
| 656Z | | | | JL | 0-0 | 28-22-31 | D02987 | | | | DED | | | TB0268Y | DED | | | ALL |
| 657 | 20 | | PQ | KL | 11-0 | 28-22-31 | D02987 | | | | 1 | | | GDX0007 | D.. | 2 | | ALL |
| 657Z | | | | KL | 0-0 | 28-22-31 | D02987 | | | | DED | | | GDX0007 | DED | | | ALL |
| 658 | 22 | | PQ | ML | 12-0 | 28-22-31 | D02987 | | | | 6 | | | TB0268X | D002 | BJ | | ALL |
| 658Z | | | | ML | 0-0 | 28-22-31 | D02987 | | | | DED | | | TB0268X | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 55

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | |
| 659 | 20 | PQ | NL | | 11-0 | 28-22-31 | D02987 | | | | GDX0007 | D.. | 2 | | ALL |
| 659Z | | | NL | | 0-0 | 28-22-31 | D02987 | DED | | | GDX0007 | DED | | | ALL |
| 664 | 24 | PK | | | 8-0 | 78-36-11 | D10168 | | | 7 | TB0458Z | 8 | BJ | | ALL |
| 665 | 24 | PK | | | 5-0 | 78-36-11 | D05664J | | | 21 | D10168 | 3 | | | 050-099 |
| 665 | 24 | PK | | | 6-0 | 78-36-11 | D05664J | | | 21 | D10168 | 3 | | | 150-199, 275-299 |
| 680 | 22 | PA | | | 6-0 | 27-62-11 | D01526 | | | 5 | D05662J | 4 | | | 050-099 |
| 680 | 22 | PA | | | 5-0 | 27-62-11 | D01526 | | | 5 | D05662J | 4 | | | 150-199, 275-299 |
| 681 | 22 | PA | | | 3-0 | 27-62-11 | D01526 | | | 3 | TB0092Y | A002 | BJ | | ALL |
| 682 | 22 | PA | | | 11-8 | 27-62-11 | D01526 | | | 4 | TB0186Y | C017 | BJ | | 050-099, 150-199 |
| 682 | 22 | PA | | | 7-0 | 27-62-11 | D01526 | | | 4 | TB0186Y | C017 | BJ | | 275-299 |
| 683 | 22 | PA | | | 6-0 | 27-62-11 | D01526 | | | 7 | TB0186Z | 8 | BJ | | ALL |
| 684 | 22 | PA | | | 11-8 | 27-62-11 | D01526 | | | 2 | TB0090G | 20 | 2 | | 050-099, 150-199 |
| 684 | 22 | PA | | | 7-0 | 27-62-11 | D01526 | | | 2 | TB0090G | 20 | 2 | | 275-299 |
| 685 | 20 | PA | | | 4-0 | 30-31-11 | D03948 | | D1 | | GDX0006 | S.. | 2 | | ALL |
| 691 | 20 | PA | | | 4-0 | 30-32-11 | D03916 | | D1 | | GDX0006 | S.. | 2 | | ALL |
| 692 | 20 | PA | | | 4-0 | 30-33-11 | D03942 | | D1 | | GDX0006 | S.. | 2 | | ALL |
| 693 | 20 | PA | | | 4-0 | 30-34-11 | D03924 | | D1 | | GDX0006 | S.. | 2 | | ALL |
| 694 | 22 | PA | | | 4-0 | 30-31-11 | D05798J | | | 12 | D03510 | A3 | | | ALL |
| 695 | 24 | PK | | | 6-0 | 30-31-11 | D05798J | | | 9 | TB0092Z | 11 | BJ | | ALL |
| 696 | 22 | PA | | | 5-0 | 30-31-11 | D10186 | | A1 | | TB0188X | D007 | BJ | | ALL |
| 697 | 24 | PK | | | 4-0 | 30-31-11 | D10186 | | X1 | | TB0092Z | 11 | BJ | | ALL |
| 700 | 22 | PA | | | 2-0 | 30-31-11 | D03510 | | D3 | | D03510 | D1 | | * | 050-099 |
| 700 | 22 | PA | | | 1-0 | 30-31-11 | D03510 | | D3 | | D03510 | D1 | | * | 150-199, 275-299 |
| 701 | 20 | PA | | | 4-0 | 30-31-11 | D03948 | | X2 | | GDX0005 | D.. | 2 | | ALL |
| 702 | 24 | PV | M | | 2-0 | 30-31-11 | D03948 | | D3 | | D03510 | B2 | | | ALL |
| 702Z | | | M | | 0-0 | 30-31-11 | D03948 | DED | | | D03510 | DED | | | ALL |
| 703 | 22 | PQ | N | | 4-0 | 30-31-11 | D03948 | | D2 | | TB0188Y | A011 | BJ | | ALL |
| 703Z | | | N | | 0-0 | 30-31-11 | D03948 | DED | | | TB0188Y | DED | | | ALL |
| 704 | 20 | PQ | P | | 4-0 | 30-31-11 | D03948 | | B2 | | GDX0007 | D.. | 2 | | ALL |
| 704Z | | | P | | 0-0 | 30-31-11 | D03948 | DED | | | GDX0007 | DED | | | ALL |
| 705 | 22 | PA | | | 2-0 | 30-31-11 | D03510 | | A2 | | D03510 | D2 | | | 050-099 |
| 705 | 22 | PA | | | 1-0 | 30-31-11 | D03510 | | A2 | | D03510 | D2 | | | 150-199, 275-299 |
| 706 | 24 | PK | | | 2-0 | 30-31-11 | TB0092Y | | C007 | BJ | TB0092Z | 11 | BJ | | 050-099 |
| 706 | 24 | PK | | | 1-0 | 30-31-11 | TB0092Y | | C007 | BJ | TB0092Z | 11 | BJ | | 150-199, 275-299 |
| 707 | 24 | PK | | | 7-0 | 30-31-11 | TB0092Z | | 11 | BJ | TB0186X | C002 | BJ | | ALL |
| 708 | 24 | PK | | | 5-0 | 30-31-11 | D05798J | | 2 | | D10186 | X2 | | | ALL |
| 709 | 22 | PA | | | 6-0 | 30-31-11 | D03510 | | A1 | | TB0196X | D004 | BJ | | ALL |
| 70D | 20 | PA | | | 3-0 | 29-11-14 | D05664J | | 51 | | TB0186Y | A017 | BJ | | ALL |
| 70E | 20 | PA | | | 3-0 | 29-11-14 | D05664J | | 50 | | TB0196Y | A008 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0140
 Page 56
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | |
| 70G | 20 | | PA | | 6-0 | 29-11-14 | TB0188X | D022 | | BJ | | D13184 | X2 | | | ALL |
| 70I | 20 | | PA | | 7-0 | 29-11-14 | D13184 | | X1 | | | TB0196Y | A008 | BJ | | ALL |
| 70J | 20 | | PA | | 7-0 | 29-11-14 | D13184 | | A2 | | | TB0196Y | A008 | BJ | | ALL |
| 70K | 20 | | PA | | 7-0 | 29-11-14 | D13184 | | A1 | | | TB0196X | C018 | BJ | | ALL |
| 70M | 20 | | PA | | 7-0 | 29-11-14 | D13184 | | A3 | | | TB0196X | D018 | BJ | | ALL |
| 70N | 20 | | PA | | 6-0 | 29-11-14 | D13186 | | A3 | | | D04801J | 11 | | | ALL |
| 70P | 20 | | PA | | 6-0 | 29-11-14 | D13186 | | A1 | | | D04801J | 16 | | | ALL |
| 70R | 20 | | PA | | 7-0 | 29-11-14 | D13186 | | A2 | | | TB0196Y | C008 | BJ | | ALL |
| 70S | 20 | | PA | | 7-0 | 29-11-14 | D13186 | | X1 | | | TB0196Y | C008 | BJ | | ALL |
| 70T | 20 | | PA | | 6-0 | 29-11-14 | D13186 | | C1 | | | TB0188X | C022 | BJ | | ALL |
| 70U | 20 | | PA | | 2-0 | 29-11-14 | D13186 | | X2 | | | GD00005 | D.. | 2 | | ALL |
| 70V | 20 | | PA | | 2-0 | 29-11-14 | TB0196Y | A008 | | BJ | | TB0196Y | C008 | BJ | | 050-099 |
| 70V | 20 | | PA | | 1-0 | 29-11-14 | TB0196Y | A008 | | BJ | | TB0196Y | C008 | BJ | | 150-199, 275-299 |
| 710 | 24 | | PV | Q | 5-0 | 30-31-11 | D03510 | | B3 | | | TB0186X | B002 | BJ | | ALL |
| 710Z | | | | Q | 0-0 | 30-31-11 | D03510 | | DED | | | TB0186X | DED | | | ALL |
| 711 | 20 | | PA | | 3-0 | 30-31-11 | D10186 | | A2 | | | GD00005 | A.. | 2 | | ALL |
| 712 | 22 | | PA | | 2-0 | 30-31-13 | D00542 | | D3 | | | D00542 | D1 | | * | 050-099 |
| 712 | 22 | | PA | | 1-0 | 30-31-13 | D00542 | | D3 | | | D00542 | D1 | | * | 150-199, 275-299 |
| 713 | 24 | | PK | | 3-0 | 30-34-11 | D10230 | | X1 | | | TB0092Z | 11 | BJ | | ALL |
| 714 | 24 | | PK | | 4-0 | 30-31-11 | D03948 | | X1 | | | TB0092Y | C007 | BJ | | ALL |
| 715 | 22 | | PA | | 2-0 | 30-31-13 | D00542 | | A2 | | | D00542 | D2 | | | 050-099 |
| 715 | 22 | | PA | | 1-0 | 30-31-13 | D00542 | | A2 | | | D00542 | D2 | | | 150-199, 275-299 |
| 71C | 20 | | PA | | 3-0 | 29-11-14 | TB0196F | A013 | | 2 | | D04801J | 21 | | | ALL |
| 71H | 20 | | PQ | CT | 3-0 | 29-11-14 | TB0196F | C013 | | 2 | | D04801J | 24 | | | ALL |
| 71HZ | | | | CT | 0-0 | 29-11-14 | TB0196F | DED | | | | D04801J | DED | | | ALL |
| 71K | 20 | | PA | | 4-0 | 29-11-14 | TB0200Y | A023 | | BJ | | D05664J | 49 | | | ALL |
| 725 | 24 | | PV | FF | 7-0 | 78-36-11 | D05193J | | 20 | | | TB0458X | B009 | BJ | | ALL |
| 725Z | | | | FF | 0-0 | 78-36-11 | D05193J | DED | | | | TB0458X | DED | | | ALL |
| 726 | 22 | | PA | | 3-0 | 30-31-21 | D05798J | | 10 | | | TB0188Y | C011 | BJ | | ALL |
| 727 | 24 | | PK | | 5-0 | 30-31-21 | D05332J | | 3 | | | D10188 | B2 | | | ALL |
| 728 | 24 | | PK | | 3-0 | 30-31-21 | D05332J | | 4 | | | TB0188Y | C011 | BJ | | ALL |
| 729 | 24 | | PV | FG | 8-0 | 78-36-11 | D05664J | | 18 | | | TB0458D | C013 | 2 | | ALL |
| 729Z | | | | FG | 0-0 | 78-36-11 | D05664J | DED | | | | TB0458D | DED | | | ALL |
| 730 | 22 | | PQ | U | 5-0 | 30-31-21 | D03510 | | C2 | | | TB0186X | A015 | BJ | | ALL |
| 730Z | | | | U | 0-0 | 30-31-21 | D03510 | DED | | | | TB0186X | DED | | | ALL |
| 731 | 24 | | PV | W | 5-0 | 30-31-21 | D10188 | | X2 | | | TB0186X | B015 | BJ | | ALL |
| 731Z | | | | W | 0-0 | 30-31-21 | D10188 | DED | | | | TB0186X | DED | | | ALL |
| 732 | 22 | | PQ | V | 5-0 | 30-31-21 | D03510 | | C1 | | | TB0186X | C015 | BJ | | ALL |
| 732Z | | | | V | 0-0 | 30-31-21 | D03510 | DED | | | | TB0186X | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 57

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 733 | 24 | | PK | | 5-0 | 30-31-21 | D10188 | | B3 | | | | TB0186X | D015 | BJ | | ALL |
| 734 | 24 | | PV | FH | 7-0 | 78-36-11 | D05193J | | 18 | | | | TB0458X | C009 | BJ | | ALL |
| 734Z | | | | FH | 0-0 | 78-36-11 | D05193J | | DED | | | | TB0458X | DED | | | ALL |
| 735 | 24 | | PV | FI | 8-0 | 78-36-11 | D05664J | | 4 | | | | TB0458X | A010 | BJ | | ALL |
| 735Z | | | | FI | 0-0 | 78-36-11 | D05664J | | DED | | | | TB0458X | DED | | | ALL |
| 736 | 24 | | PV | Y | 5-0 | 30-31-21 | D10188 | | X1 | | | | TB0186X | A016 | BJ | | ALL |
| 736Z | | | | Y | 0-0 | 30-31-21 | D10188 | | DED | | | | TB0186X | DED | | | ALL |
| 740 | 24 | | PK | | 5-0 | 36-11-51 | D05798J | | 44 | | | | D10526 | 5 | | | 050-099, 150-155, 163-165, 275-276 |
| 740 | 24 | | PK | | 5-0 | 36-11-51 | D05798J | | 18 | | | | D10526 | 5 | | | 156-162, 166-199, 277-299 |
| 741 | 22 | | PA | | 2-0 | 36-11-51 | D10526 | | 4 | | | | GDX0005 | D.. | 2 | | ALL |
| 742 | 24 | | PV | FJ | 7-0 | 78-36-11 | D05193J | | 19 | | | | TB0458D | C014 | 2 | | ALL |
| 742Z | | | | FJ | 0-0 | 78-36-11 | D05193J | | DED | | | | TB0458D | DED | | | ALL |
| 744 | 24 | | PV | FM | 8-0 | 78-36-11 | D05664J | | 20 | | | | TB0458X | A009 | BJ | | ALL |
| 744Z | | | | FM | 0-0 | 78-36-11 | D05664J | | DED | | | | TB0458X | DED | | | ALL |
| 747 | 24 | | PK | | 5-0 | 30-34-11 | D05798J | | 25 | | | | D10230 | X2 | | | ALL |
| 749 | 20 | | PA | | 4-0 | 34-12-12 | D03952 | | C3 | | | | GDX0007 | D.. | 2 | | ALL |
| 750 | 24 | | PK | | 4-0 | 34-12-12 | D03952 | | A2 | | | | D04801J | 3 | | | ALL |
| 751 | 20 | | PA | | 4-0 | 34-12-12 | D03948 | | C3 | | | | GDX0007 | D.. | 2 | | ALL |
| 752 | 20 | | PA | | 4-0 | 73-21-12 | D03924 | | C3 | | | | GDX0006 | D.. | 2 | | ALL |
| 753 | 22 | | PA | | 6-0 | 78-36-11 | D05664J | | 35 | | | | D10168 | 2 | | | ALL |
| 754 | 22 | | PA | | 8-0 | 78-36-11 | TB0458Y | | A005 | BJ | | | D10168 | 4 | | | 050-099 |
| 754 | 22 | | PA | | 7-0 | 78-36-11 | TB0458Y | | A005 | BJ | | | D10168 | 4 | | | 150-199, 275-299 |
| 756 | 24 | | PK | | 8-0 | 78-36-11 | D05664J | | 34 | | | | TB0458Z | 8 | BJ | | ALL |
| 757 | 24 | | PK | | 5-0 | 32-09-13 | D10188 | | A3 | | | | TB0188Y | A003 | BJ | | ALL |
| 758 | 24 | | PK | | 5-0 | 32-09-13 | D10188 | | A2 | | | | TB0188X | B007 | BJ | | ALL |
| 759 | 24 | | PK | | 4-0 | 30-31-11 | D05798J | | 13 | | | | TB0200X | A003 | BJ | | ALL |
| 760 | 22 | | PA | | 2-2 | 33-51-11 | D05664J | | 36 | | | | TB0188X | C006 | BJ | | ALL |
| 763 | 22 | | PA | | 4-0 | 29-11-22 | D05662J | | 5 | | | | TB0200D | C025 | 2 | | 050-099 |
| 763 | 22 | | PA | | 3-6 | 29-11-22 | D05662J | | 5 | | | | TB0200D | C025 | 2 | | 150-199, 275-299 |
| 764 | 22 | | PA | | 3-0 | 29-11-22 | D05798J | | 42 | | | | TB0188Z | 13 | BJ | | ALL |
| 765 | 24 | | PK | | 8-0 | 27-58-11 | TB0268X | | A002 | BJ | | | TB0200Z | 22 | BJ | | ALL |
| 766 | 24 | | PK | | 8-0 | 27-58-11 | TB0268X | | B002 | BJ | | | TB0200Z | 22 | BJ | | ALL |
| 767 | 24 | | PK | | 4-0 | 29-11-12 | D05798J | | 45 | | | | TB0196D | A022 | 2 | | ALL |
| 768 | 24 | | PK | | 4-0 | 29-11-22 | D05798J | | 46 | | | | TB0196D | A023 | 2 | | ALL |
| 769 | 24 | | PK | | 4-0 | 30-34-11 | D03924 | | X1 | | | | TB0092Y | A008 | BJ | | ALL |
| 780 | 24 | | PK | | 3-0 | 29-11-22 | D10414 | | 2 | | | | TB0092Z | 12 | BJ | | ALL |
| 781 | 24 | | PK | | 3-0 | 29-11-22 | D10414 | | 7 | | | | TB0092Z | 12 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 58

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0144 | 286T0144 | | | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | |
| 782 | 24 | | PK | 6-0 | 29-11-22 | D10414 | | 3 | | | | | D05662J | 14 | | | ALL |
| 783 | 24 | | PK | 7-0 | 29-11-22 | TB0092Z | | 12 | BJ | | | | TB0186D | C019 | 2 | | ALL |
| 784 | 24 | | PK | 6-0 | 29-11-22 | TB0092Z | | 12 | BJ | | | | D05662J | 13 | | | 050-099 |
| 784 | 24 | | PK | 6-6 | 29-11-22 | TB0092Z | | 12 | BJ | | | | D05662J | 13 | | | 150-199, 275-299 |
| 785 | 24 | | PK | 5-0 | 29-11-22 | D01268 | | A1 | | | | | TB0186D | A019 | 2 | | ALL |
| 786 | 24 | | PK | 3-0 | 29-11-22 | D01268 | | A2 | | | | | D10414 | 5 | | | ALL |
| 787 | 24 | | PK | 5-0 | 21-44-21 | D10494 | | A2 | | | | | TB0188X | C019 | BJ | | ALL |
| 788 | 20 | | PA | 2-0 | 21-44-21 | D10494 | | A3 | | | | | GD0005 | D.. | 2 | | ALL |
| 789 | 24 | | PK | 5-0 | 21-44-21 | D10494 | | X1 | | | | | TB0188Z | 14 | BJ | | ALL |
| 790 | 24 | | PK | 5-0 | 21-44-21 | D10494 | | X2 | | | | | D05798J | 47 | | | ALL |
| 791 | 24 | | PK | 5-0 | 36-11-41 | D01722 | | A3 | | | | | TB0200X | C003 | BJ | | ALL |
| 792 | 24 | | PK | 5-0 | 36-11-41 | D01722 | | A2 | | | | | TB0200X | D003 | BJ | | ALL |
| 793 | 24 | | PK | 6-0 | 36-11-41 | D10526 | | 2 | | | | | TB0200X | A004 | BJ | | ALL |
| 794 | 24 | | PK | 6-0 | 36-11-41 | D10526 | | 1 | | | | | TB0200X | B004 | BJ | | ALL |
| 795 | 22 | | PA | 5-0 | 36-11-51 | D10526 | | 6 | | | | | TB0186Y | A004 | BJ | | ALL |
| 796 | 22 | | PA | 5-0 | 36-11-51 | D10526 | | 12 | | | | | D05798J | 48 | | | ALL |
| 797 | 22 | | PA | 3-0 | 27-62-11 | TB0200D | | A017 | 2 | | | | TB0186Z | 8 | BJ | | ALL |
| 798 | 22 | | PA | 3-0 | 27-62-11 | TB0200R | | A020 | 2 | | | | TB0186Y | C005 | BJ | | ALL |
| 799 | 22 | | PA | 3-0 | 27-62-11 | TB0200R | | C020 | 2 | | | | TB0200D | C017 | 2 | | 050-099 |
| 799 | 22 | | PA | 1-0 | 27-62-11 | TB0200R | | C020 | 2 | | | | TB0200D | C017 | 2 | | 150-199, 275-299 |
| 820 | 22 | | PA | 8-0 | 78-36-11 | TB0458Y | | A005 | BJ | | | | D04801J | 13 | | | ALL |
| 825 | 20 | | PQ | FA | 14-0 | 78-34-11 | | 17 | | | | | TB0266X | C009 | BJ | | 050-099 |
| 825 | 20 | | PQ | FA | 7-0 | 78-34-11 | | 17 | | | | | TB0266X | C009 | BJ | | 150-199, 275-299 |
| 825Z | | | | FA | 0-0 | 78-34-11 | | | | AA | | | TB0266X | | | AB | ALL |
| 826 | 20 | | PQ | FB | 14-0 | 78-34-11 | | 18 | | | | | TB0266X | D009 | BJ | | 050-099 |
| 826 | 20 | | PQ | FB | 7-0 | 78-34-11 | | 18 | | | | | TB0266X | D009 | BJ | | 150-199, 275-299 |
| 826Z | | | | FB | 0-0 | 78-34-11 | | | | AA | | | TB0266X | | | AB | ALL |
| 827 | 20 | | PA | | 10-0 | 78-34-11 | | | | AA | | | GD0007 | S.. | 2 | | 050-099 |
| 827 | 20 | | PA | | 5-6 | 78-34-11 | | | | AA | | | GD0007 | S.. | 2 | | 150-199, 275-299 |
| 833 | 22 | | PA | | 7-0 | 78-34-11 | | 13 | | | | | TB0458X | B001 | BJ | | 050-099 |
| 833 | 22 | | PA | | 4-6 | 78-34-11 | | 13 | | | | | TB0458X | B001 | BJ | | 150-199, 275-299 |
| 834 | 22 | | PQ | T4 | 7-0 | 78-34-11 | | 14 | | | | | TB0458X | A001 | BJ | | 050-099 |
| 834 | 22 | | PQ | T4 | 4-6 | 78-34-11 | | 14 | | | | | TB0458X | A001 | BJ | | 150-199, 275-299 |
| 834Z | | | | T4 | 0-0 | 78-34-11 | | | | AE | | | TB0458X | C002 | BJ | | ALL |
| 838 | 20 | | PQ | T8 | 7-0 | 78-34-11 | | A006 | BJ | | | | D05193J | 22 | | | 050-099 |
| 838 | 20 | | PQ | T8 | 4-6 | 78-34-11 | | A006 | BJ | | | | D05193J | 22 | | | 150-199, 275-299 |
| 838Z | | | | T8 | 0-0 | 78-34-11 | | | | AE | | | TB0458Y | | | AF | ALL |
| 839 | 20 | | PQ | BJ | 7-0 | 78-34-11 | | 17 | | | | | TB0458Y | C006 | BJ | | 050-099 |
| 839 | 20 | | PQ | BJ | 4-6 | 78-34-11 | | 17 | | | | | TB0458Y | C006 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 59

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|---|-------|-------------|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0144 | 286T0144 | P33-L2-MISC ELECTRICAL PANEL (continued) | | | | | | | | | | | | | | |
| 839Z | | | | BJ | 0-0 | 78-34-11 | D05193J | | | | AE | TB0458Y | | | AF | ALL |
| 840 | 20 | PA | | | 3-0 | 78-34-11 | TB0458Y | | | | AF | GDX0016 | S.. | 2 | | 050-099 |
| 840 | 20 | PA | | | 2-0 | 78-34-11 | TB0458Y | | | | AF | GDX0016 | S.. | 2 | | 150-199, 275-299 |
| 841 | 22 | PA | | | 8-0 | 78-36-11 | D04801J | 17 | | | | TB0458D | A013 | 2 | | 050-099 |
| 841 | 22 | PA | | | 4-6 | 78-36-11 | D04801J | 17 | | | | TB0458D | A013 | 2 | | 150-199, 275-299 |
| 851 | 22 | PA | | | 8-0 | 78-36-11 | D04801J | 4 | | | | TB0458D | A014 | 2 | | ALL |
| 855 | 22 | PA | | | 8-0 | 78-36-11 | TB0458Z | 8 | BJ | | | D04801J | 12 | | | ALL |
| 878 | 20 | PA | | | 8-0 | 78-34-11 | D05664J | 1 | | | | TB0458X | C001 | BJ | | ALL |
| 879 | 20 | PQ | X9 | | 8-0 | 78-34-11 | D05664J | 12 | | | | TB0458Z | 7 | BJ | | ALL |
| 879Z | | | X9 | | 0-0 | 78-34-11 | D05664J | 11 | | | | TB0458Z | | | AZ | ALL |
| 880 | 22 | PA | | | 8-0 | 78-36-11 | D05662J | 7 | | | | TB0458Y | A005 | BJ | | 050-099 |
| 880 | 22 | PA | | | 4-6 | 78-36-11 | D05662J | 7 | | | | TB0458Y | A005 | BJ | | 150-199, 275-299 |
| 882 | 20 | PA | | | 2-0 | 78-34-11 | TB0458Z | | | | AZ | GDX0016 | S.. | 2 | | ALL |
| A-A | | | | A | 0-0 | 27-58-11 | M00605 | 1 | | | | TB0268X | A001 | BJ | | 050-099 |
| A-A | | | | | 0-0 | 27-58-11 | M00605 | 1 | | | | TB0268X | A001 | BJ | | 150-199, 275-299 |
| A-B | | | | A | 0-0 | 27-58-11 | M00605 | 2 | | | | TB0268X | B001 | BJ | | 050-099 |
| A-B | | | | | 0-0 | 27-58-11 | M00605 | 2 | | | | TB0268X | B001 | BJ | | 150-199, 275-299 |
| A-C | | | | A | 0-0 | 27-58-11 | M00605 | 3 | | | | TB0268X | A002 | BJ | | 050-099 |
| A-C | | | | | 0-0 | 27-58-11 | M00605 | 3 | | | | TB0268X | A002 | BJ | | 150-199, 275-299 |
| A-D | | | | A | 0-0 | 27-58-11 | M00605 | 4 | | | | GDX0005 | A.. | 2 | | 050-099 |
| A-D | | | | | 0-0 | 27-58-11 | M00605 | 4 | | | | GDX0005 | A.. | 2 | | 150-199, 275-299 |
| A-E | | | | B | 0-0 | 27-58-11 | M00606 | 1 | | | | TB0268X | C001 | BJ | | 050-099 |
| A-E | | | | | 0-0 | 27-58-11 | M00606 | 1 | | | | TB0268X | C001 | BJ | | 150-199, 275-299 |
| A-F | | | | B | 0-0 | 27-58-11 | M00606 | 2 | | | | TB0268X | D001 | BJ | | 050-099 |
| A-F | | | | | 0-0 | 27-58-11 | M00606 | 2 | | | | TB0268X | D001 | BJ | | 150-199, 275-299 |
| A-G | | | | B | 0-0 | 27-58-11 | M00606 | 3 | | | | TB0268X | B002 | BJ | | 050-099 |
| A-G | | | | | 0-0 | 27-58-11 | M00606 | 3 | | | | TB0268X | B002 | BJ | | 150-199, 275-299 |
| A-H | | | | B | 0-0 | 27-58-11 | M00606 | 4 | | | | GDX0005 | A.. | 2 | | 050-099 |
| A-H | | | | | 0-0 | 27-58-11 | M00606 | 4 | | | | GDX0005 | A.. | 2 | | 150-199, 275-299 |
| FRA | | | | | 0-0 | 78-34-11 | D05662J | | | | AA | D05662J | 16 | | | ALL |
| FRB | | | | | 0-0 | 78-34-11 | TB0266X | | | | AB | TB0266X | B009 | BJ | | ALL |
| FRE | | | | | 0-0 | 78-34-11 | D05193J | | | | AE | D05193J | 15 | | | ALL |
| W0145 | 286T0145 | E2-3 R,SHELF | | | | | | | | | | | | | | |
| 001 | 22 | PQ | AA | | 3-9 | 34-61-21 | D04253P | 12 | | | | D00353C | 1 | | | ALL |
| 001Z | | | AA | | 0-0 | 34-61-21 | D04253P | | DED | | | D00353C | DED | | | ALL |
| 002 | 24 | PV | AB | | 3-8 | 34-61-21 | D04253P | 1 | | | | D04433P | 7 | | | ALL |
| 002Z | | | AB | | 0-0 | 34-61-21 | D04253P | | DED | | | D04433P | DED | | | ALL |
| 003 | 24 | PK | | | 3-4 | 34-61-21 | D04505P | 32 | | | | D04433P | 10 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0140
 Page 60
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | | | |
| 004 | 22 | | PA | | 3-10 | 27-09-14 | D05065P | | | | 2 | | | D05407P | 2 | | | ALL |
| 007 | 20 | | PA | | 2-7 | 34-61-21 | D00353C | | | | 7 | | | GDX0013 | A.. | 2 | | ALL |
| 008 | 20 | | PA | | 2-7 | 34-61-21 | D00353C | | | | 8 | | | GDX0013 | D.. | 2 | | ALL |
| 010 | 24 | | PK | | 5-3 | 34-61-23 | D00353A | | | | K11 | | | TB0145Y | A006 | BJ | | 050-099, 150-199, 275-276 |
| 010 | 24 | | PK | | 5-3 | 34-61-23 | D00353A | | | | K11 | | | TB0145Y | A012 | BJ | | 277-299 |
| 011 | 22 | | PQ | AK | 3-5 | 34-61-23 | D00353B | | | | A13 | | | TB0145X | A158 | BJ | | ALL |
| 011Z | | | | AK | 0-0 | 34-61-23 | D00353B | | | | DED | | | TB0145X | DED | | | ALL |
| 012 | 24 | | PV | AL | 3-5 | 34-61-23 | D00353A | | | | K09 | | | TB0145X | A160 | BJ | | ALL |
| 012Z | | | | AL | 0-0 | 34-61-23 | D00353A | | | | DED | | | TB0145X | DED | | | ALL |
| 013 | 24 | | PK | | 4-3 | 34-61-24 | TB0145Y | | | | A147 | BJ | | D04667P | 1 | | | ALL |
| 015 | 22 | | PA | | 2-7 | 34-61-24 | D00353B | | | | K05 | | | GDX0009 | D.. | 2 | | ALL |
| 016 | 22 | | PA | | 2-7 | 34-61-24 | D00353B | | | | K03 | | | GDX0009 | D.. | 2 | | ALL |
| 01C | 22 | | PA | | 3-2 | 34-12-62 | D04505P | | | | 20 | | | D03693P | 5 | | | 050-099, 150-199, 280-299 |
| 01C | 22 | | PA | | 3-2 | 34-12-62 | D03693P | | | | 5 | | | D04505P | 20 | | | 275-278 |
| 01DB | 24 | | PW | D | 4-0 | 34-12-62 | D03693P | | | | 19 | | | TB0145Y | C167 | BJ | | 050-099, 150-156, 162-166, 275-278 |
| 01DB | 24 | | PW | G4 | 4-0 | 34-12-62 | D03693P | | | | 19 | | | TB0145Y | C167 | BJ | | 157, 167-199, 280-299 |
| 01DR | 24 | | PW | D | 0-0 | 34-12-62 | D03693P | | | | 20 | | | TB0145Y | A167 | BJ | | 050-099, 150-156, 162-166, 275-278 |
| 01DR | 24 | | PW | G4 | 0-0 | 34-12-62 | D03693P | | | | 20 | | | TB0145Y | A167 | BJ | | 157, 167-199, 280-299 |
| 01DZ | | | | D | 0-0 | 34-12-62 | D03693P | | | | 21 | | | GDY0011 | S.. | 2 | | 050-099, 150-156, 162-166, 275-278 |
| 01DZ | | | | G4 | 0-0 | 34-12-62 | D03693P | | | | 21 | | | GDY0011 | S.. | 2 | | 157, 167-199, 280-299 |
| 01R | 22 | | PA | | 2-5 | 34-61-23 | D00353B | | | | K11 | | | GDX0012 | D.. | 2 | | 150-199 |
| 022 | 24 | | PK | | 3-7 | 34-61-13 | D05713P | | | | 1 | | | TB0145Y | A006 | BJ | | 050-099, 150-199, 275-276 |
| 022 | 24 | | PK | | 3-6 | 34-61-13 | D05713P | | | | 1 | | | TB0145Y | A012 | BJ | | 277-299 |
| 023 | 22 | | PA | | 3-6 | 34-61-13 | D05713P | | | | 11 | | | TB0145Y | C009 | BJ | | 050-099, 150-199, 275-276 |
| 023 | 22 | | PA | | 3-4 | 34-61-13 | D05713P | | | | 11 | | | TB0145Y | C015 | BJ | | 277-299 |
| 024 | 24 | | PK | | 4-0 | 31-31-22 | D05439P | | | | 10 | | | TB0145X | C163 | BJ | | ALL |
| 025 | 22 | | PA | | 3-10 | 27-09-14 | D05065P | | | | 9 | | | D05407P | 1 | | | ALL |
| 027 | 22 | | PA | | 5-3 | 34-61-23 | D00353B | | | | A15 | | | TB0145Y | C009 | BJ | | 050-099, 150-199, 275-276 |
| 027 | 22 | | PA | | 5-1 | 34-61-23 | D00353B | | | | A15 | | | TB0145Y | C015 | BJ | | 277-299 |
| 029 | 22 | | PA | | 2-5 | 34-61-23 | D00353B | | | | B15 | | | GDX0012 | D.. | 2 | | 157, 167-199, 275-299 |
| 030 | 22 | | PA | | 2-7 | 34-61-24 | D00353A | | | | K07 | | | GDX0009 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 61

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 032 | 24 | | PK | | 3-10 | 34-61-23 | D00353B | | B14 | | D04819P | | 34 | | ALL |
| 033 | 24 | | PK | | 3-10 | 34-61-23 | D00353B | | C14 | | D04819P | | 25 | | ALL |
| 034 | 24 | | PK | | 3-10 | 34-61-23 | D00353B | | F14 | | D04819P | | 26 | | ALL |
| 035 | 24 | | PK | | 3-10 | 34-61-23 | D00353B | | G13 | | D04819P | | 27 | | ALL |
| 036 | 24 | | PK | | 3-10 | 34-61-23 | D00353B | | J14 | | D04819P | | 28 | | ALL |
| 037 | 24 | | PV | BL | 3-10 | 34-61-23 | D00353B | | J13 | | D04819P | | 29 | | ALL |
| 037Z | | | | BL | 0-0 | 34-61-23 | D00353B | | DED | | D04819P | DED | | | ALL |
| 038 | 24 | | PV | BM | 3-10 | 34-61-23 | D00353B | | A14 | | D04819P | | 30 | | ALL |
| 038Z | | | | BM | 0-0 | 34-61-23 | D00353B | | DED | | D04819P | DED | | | ALL |
| 039 | 24 | | PV | BN | 3-10 | 34-61-23 | D00353B | | E13 | | D04819P | | 31 | | ALL |
| 039Z | | | | BN | 0-0 | 34-61-23 | D00353B | | DED | | D04819P | DED | | | ALL |
| 040 | 24 | | PV | BO | 3-10 | 34-61-23 | D00353B | | G14 | | D04819P | | 32 | | ALL |
| 040Z | | | | BO | 0-0 | 34-61-23 | D00353B | | DED | | D04819P | DED | | | ALL |
| 041 | 24 | | PV | BP | 3-10 | 34-61-23 | D00353B | | F13 | | D04819P | | 33 | | ALL |
| 041Z | | | | BP | 0-0 | 34-61-23 | D00353B | | DED | | D04819P | DED | | | ALL |
| 043 | 22 | | PA | | 2-7 | 34-61-24 | D00353B | | H11 | | GDX0009 | D.. | 2 | | 150, 152-165, 167-199, 275-299 |
| 043 | 22 | | PA | | 2-7 | 34-61-24 | D00353B | | D11 | | GDX0009 | D.. | 2 | | 151, 166 |
| 046 | 24 | | PK | | 4-0 | 31-31-22 | D05439P | | 9 | | TB0145X | D163 | BJ | | ALL |
| 048 | 20 | | PQ | BW | 4-7 | 34-53-21 | D04253P | | 5 | | TB0145Y | C044 | BJ | | 050-099, 155-199, 275-299 |
| 048 | 20 | | PQ | BW | 4-7 | 34-53-21 | D04253P | | 5 | | TB0145G | 41 | 2 | | 150-154 |
| 048Z | | | | BW | 0-0 | 34-53-21 | D04253P | | DED | | TB0145Y | DED | | | 050-099, 155-199, 275-299 |
| 048Z | | | | BW | 0-0 | 34-53-21 | D04253P | | DED | | TB0145G | DED | | | 150-154 |
| 051 | 20 | | PQ | CA | 5-0 | 34-51-21 | D00357C | | 2 | | D04253P | 4 | | | ALL |
| 051Z | | | | CA | 0-0 | 34-51-21 | D00357C | | DED | | D04253P | DED | | | ALL |
| 052 | 20 | | PA | | 2-7 | 34-51-21 | D00357C | | 3 | | GDX0005 | A.. | 2 | | ALL |
| 053 | 20 | | PA | | 2-7 | 34-51-21 | D00357C | | 4 | | GDX0005 | S.. | 2 | | ALL |
| 054 | 22 | | PA | | 4-1 | 34-51-21 | D00357B | | A11 | | TB0145Y | C009 | BJ | | 050-099, 150-199, 275-276 |
| 054 | 22 | | PA | | 3-10 | 34-51-21 | D00357B | | A11 | | TB0145Y | C015 | BJ | | 277-299 |
| 055 | 24 | | PK | | 4-1 | 34-51-21 | D00357B | | A15 | | TB0145Y | A009 | BJ | | 050-099, 150-199, 275-276 |
| 055 | 24 | | PK | | 3-10 | 34-51-21 | D00357B | | A15 | | TB0145Y | A015 | BJ | | 277-299 |
| 056 | 22 | | PA | | 7-0 | 34-51-21 | TB0145Y | | C009 | BJ | D04377P | 6 | | | 050-099, 150-199, 275-276 |
| 056 | 22 | | PA | | 6-10 | 34-51-21 | TB0145Y | | C015 | BJ | D04377P | 6 | | | 277-299 |
| 057 | 22 | | PA | | 2-7 | 34-51-21 | D00357B | | D02 | | GDX0005 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 62

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | | |
| 058 | 24 | | PK | 3-10 | 31-51-41 | D04819P | | 21 | | | | | D05715J | 23 | | | 050-099 |
| 058 | 24 | | PK | 3-10 | 31-51-41 | TB0145D | | C125 | 2 | | | | D05715J | 23 | | | 150-199, 275-276 |
| 058 | 24 | | PK | 3-7 | 31-51-41 | TB0145D | | C096 | 2 | | | | D05715J | 23 | | | 277-299 |
| 059 | 22 | | PA | 4-8 | 34-53-21 | D04697P | | | 3 | | | | TB0145Y | C044 | BJ | | 050-099, 155-199, 275-299 |
| 059 | 22 | | PA | 4-8 | 34-53-21 | D04697P | | | 3 | | | | TB0145G | 41 | 2 | | 150-154 |
| 060 | 24 | | PK | 3-10 | 31-51-21 | D04819P | | | 14 | | | | D05715J | 1 | | | 150-154, 275 |
| 063 | 24 | | PK | 3-11 | 31-51-11 | D04819P | | | 3 | | | | D05065P | 11 | | | ALL |
| 064 | 24 | | PK | 4-3 | 31-51-21 | D04819P | | | 10 | | | | D04667P | 3 | | | ALL |
| 065 | 24 | | PK | 4-3 | 31-51-33 | D04819P | | | 11 | | | | D04667P | 22 | | | ALL |
| 068 | 24 | | PK | 6-1 | 34-53-21 | D00359B | | H03 | | | | | D04697P | 9 | | | 050-099, 150-156, 162-166, 275-276 |
| 070 | 24 | | PK | 6-1 | 34-53-21 | D00359B | | K03 | | | | | D04697P | 7 | | | ALL |
| 072 | 20 | | PA | 2-1 | 34-53-21 | D00359C | | | 7 | | | | GD0003 | A.. | 2 | | ALL |
| 073 | 20 | | PA | 2-1 | 34-53-21 | D00359C | | | 11 | | | | GD0003 | D.. | 2 | | ALL |
| 075 | 22 | | PA | 5-5 | 31-31-14 | D04767P | | | 53 | | | | TB0145X | A107 | BJ | | 050-099 |
| 075 | 22 | | PA | 5-4 | 31-31-14 | D04767P | | | 53 | | | | TB0145X | A107 | BJ | | 150-199, 275-276 |
| 075 | 22 | | PA | 5-2 | 31-31-14 | D04767P | | | 53 | | | | TB0145X | A113 | BJ | | 277-299 |
| 076 | 22 | | PA | 3-10 | 34-53-21 | D00359C | | | 1 | | | | TB0145Y | C044 | BJ | | 050-099, 155-199, 275-299 |
| 076 | 22 | | PA | 3-10 | 34-53-21 | D00359C | | | 1 | | | | TB0145G | 41 | 2 | | 150-154 |
| 077 | 24 | | PK | 4-3 | 34-53-21 | D04697P | | | 2 | | | | D04667P | 2 | | | ALL |
| 078 | 24 | | PK | 6-1 | 34-53-21 | D04697P | | | 6 | | | | D00359A | G07 | | | ALL |
| 079 | 24 | | PK | 6-1 | 34-53-21 | D00359A | | J05 | | | | | D04697P | 8 | | | 050-099, 155-199, 275-299 |
| 079 | 24 | | PK | 6-1 | 34-53-21 | D04697P | | | 8 | | | | D00359A | J05 | | | 150-154 |
| 081 | 24 | | PK | 5-1 | 34-53-13 | D05713P | | | 27 | | | | D04697P | 5 | | | ALL |
| 085 | 22 | | PQ | DJ | 6-8 | 34-55-21 | D00361C | | 1 | | | | D04253P | 6 | | | ALL |
| 085Z | | | DJ | | 0-0 | 34-55-21 | D00361C | | DED | | | | D04253P | DED | | | ALL |
| 086 | 20 | | PA | | 2-4 | 34-55-21 | D00361C | | 7 | | | | GD0001 | A.. | 2 | | ALL |
| 087 | 20 | | PA | | 2-4 | 34-55-21 | D00361C | | 11 | | | | GD0001 | S.. | 2 | | ALL |
| 088 | 24 | | PK | | 3-1 | 34-55-21 | D00361B | | B05 | | | | TB0145Y | A006 | BJ | | 050-099, 150-199, 275-276 |
| 088 | 24 | | PK | | 3-1 | 34-55-21 | D00361B | | B05 | | | | TB0145Y | A012 | BJ | | 277-299 |
| 089 | 24 | | PK | | 3-1 | 34-55-21 | D00361B | | K05 | | | | TB0145Y | A009 | BJ | | 050-099, 150-199, 275-276 |
| 089 | 24 | | PK | | 3-2 | 34-55-21 | D00361B | | K05 | | | | TB0145Y | A015 | BJ | | 277-299 |
| 090 | 24 | | PK | | 6-4 | 34-55-21 | TB0145Y | | A009 | BJ | | | D04667P | 37 | | | 050-099, 150-199, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 63

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 090 | 24 | | PK | | 6-2 | 34-55-21 | TB0145Y | A015 | BJ | | D04667P | | 37 | | 277-299 |
| 091 | 24 | | PK | | 7-1 | 34-55-21 | TB0145Y | A006 | BJ | | D04377P | | 7 | | 050-099, 150-199, 275-276 |
| 091 | 24 | | PK | | 7-0 | 34-55-21 | TB0145Y | A012 | BJ | | D04377P | | 7 | | 277-299 |
| 093 | 24 | | PK | | 3-10 | 31-51-21 | D05715J | | | 4 | D04819P | | 5 | | 150-154, 275 |
| 094 | 24 | | PK | | 3-10 | 31-51-21 | D05715J | | | 22 | D04819P | | 4 | | 150-154, 275 |
| 095 | 24 | | PK | | 3-10 | 31-51-21 | D05715J | | | 24 | D04819P | | 12 | | 150-154, 275 |
| 097 | 24 | | PK | | 6-1 | 34-31-21 | D04821P | | | 1 | TB0145Y | A009 | BJ | | 050-099, 150-199, 275-276 |
| 097 | 24 | | PK | | 5-4 | 34-31-21 | D04821P | | | 1 | TB0145Y | A015 | BJ | | 277-299 |
| 098 | 24 | | PK | | 3-11 | 34-61-25 | D05439P | | | 1 | TB0145D | C076 | 2 | | 050-099, 150-199, 275-276 |
| 098 | 24 | | PK | | 3-7 | 34-61-25 | D05439P | | | 1 | TB0145D | C190 | 2 | | 277-299 |
| 101 | 22 | | PA | | 3-8 | 34-12-62 | D04505P | | | 28 | TB0145Y | A168 | BJ | | ALL |
| 102 | 22 | | PA | | 4-3 | 31-31-11 | TB0145X | A146 | BJ | | D04667P | | 12 | | ALL |
| 104 | 24 | | PK | | 4-6 | 31-31-12 | TB0145Y | A139 | BJ | | D04667P | | 10 | | ALL |
| 105 | 24 | | PV | EE | 4-10 | 31-31-12 | TB0145Z | | | 131 | D04667P | | 11 | | ALL |
| 105Z | | | | EE | 0-0 | 31-31-12 | TB0145Z | DED | | | D04667P | DED | | | ALL |
| 106 | 22 | | PQ | EF | 4-10 | 31-31-11 | TB0145Z | | | 132 | D04667P | | 4 | | ALL |
| 106Z | | | | EF | 0-0 | 31-31-11 | TB0145Z | DED | | | D04667P | DED | | | ALL |
| 107 | 22 | | PQ | EG | 4-10 | 31-31-11 | TB0145Y | A134 | BJ | | D04667P | | 5 | | ALL |
| 107Z | | | | EG | 0-0 | 31-31-11 | TB0145Y | DED | | | D04667P | DED | | | ALL |
| 110 | 24 | | PK | | 4-3 | 31-31-17 | TB0145X | B142 | BJ | | D04811P | | 1 | | ALL |
| 111 | 24 | | PK | | 6-4 | 31-31-17 | TB0145X | A108 | BJ | | D04811P | | 2 | | 050-099 |
| 111 | 24 | | PK | | 6-3 | 31-31-17 | TB0145X | A108 | BJ | | D04811P | | 2 | | 150-199, 275-276 |
| 111 | 24 | | PK | | 6-1 | 31-31-17 | TB0145X | A114 | BJ | | D04811P | | 2 | | 277-299 |
| 112 | 24 | | PK | | 4-3 | 31-31-17 | TB0145X | D142 | BJ | | D04811P | | 3 | | ALL |
| 115 | 24 | | PK | | 3-4 | 31-31-17 | D04811P | | | 29 | TB0145R | C187 | 2 | | ALL |
| 116 | 24 | | PK | | 4-3 | 31-31-17 | D04811P | | | 30 | TB0145X | B141 | BJ | | 050-099, 150-154, 162-163, 275-276 |
| 116 | 24 | | PK | | 3-4 | 31-31-17 | D04811P | | | 30 | TB0145R | C188 | 2 | | 155-157, 164-199, 277-299 |
| 117 | 24 | | PV | EQ | 4-10 | 31-31-11 | D04667P | | | 31 | TB0145Z | | 131 | BJ | ALL |
| 117Z | | | | EQ | 0-0 | 31-31-11 | D04667P | DED | | | TB0145Z | DED | | | ALL |
| 118 | 24 | | PK | | 4-6 | 31-31-11 | D04667P | | | 30 | TB0145Y | C140 | BJ | | ALL |
| 119 | 24 | | PK | | 3-6 | 34-61-17 | TB0145Y | A078 | BJ | | D04811P | | 43 | | 157, 167-199 |
| 119 | 24 | | PK | | 6-4 | 34-61-17 | TB0145Y | C012 | BJ | | D04811P | | 43 | | 277-299 |
| 121 | 22 | | PA | | 4-4 | 31-31-18 | D04821P | | | 43 | TB0145X | C037 | BJ | | ALL |
| 122 | 22 | | PA | | 4-4 | 31-31-18 | D04821P | | | 44 | TB0145X | B037 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0140
Page 64
Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 123 | 22 | PA | | 4-4 | 31-31-18 | D04821P | | 45 | | | | TB0145X | A037 | BJ | | ALL |
| 124 | 22 | PA | | 4-4 | 31-31-18 | D04821P | | 46 | | | | TB0145X | D037 | BJ | | ALL |
| 146 | 24 | PK | | 4-1 | 34-61-26 | D04253P | | 14 | | | | TB0145Z | 65 | BJ | | ALL |
| 149 | 24 | PK | | 4-2 | 31-51-33 | D04819P | | 2 | | | | D04811P | 24 | | | ALL |
| 150 | 24 | PK | | 6-8 | 31-51-33 | D04697P | | 1 | | | | TB0145Y | A008 | BJ | | 050-099, 150-199, 275-276 |
| 150 | 24 | PK | | 6-5 | 31-51-33 | D04697P | | 1 | | | | TB0145Y | A014 | BJ | | 277-299 |
| 152 | 24 | PK | | 4-2 | 23-21-11 | D04819P | | 17 | | | | D04811P | 31 | | | ALL |
| 154 | 24 | PK | | 3-10 | 32-42-11 | D04667P | | 29 | | | | D04505P | 27 | | | ALL |
| 158 | 24 | PV | GH | 5-1 | 31-31-12 | D05439P | | REF | JB | | | TB0145Z | 131 | BJ | | ALL |
| 158Z | | | GH | 0-0 | 31-31-12 | D05439P | | DED | | | | TB0145Z | DED | | | ALL |
| 159 | 24 | PK | | 4-9 | 31-31-12 | D05439P | | REF | JB | | | TB0145Y | C139 | BJ | | ALL |
| 161 | 24 | PK | | 3-8 | 34-61-24 | D00353A | | K01 | | | | TB0145Y | A147 | BJ | | ALL |
| 162 | 24 | PK | | 3-8 | 34-61-24 | D00353A | | F09 | | | | TB0145Y | A147 | BJ | | ALL |
| 163 | 22 | PA | | 2-6 | 34-61-23 | D00353B | | B13 | | | | GDX0012 | D.. | 2 | | 050-099 |
| 163 | 22 | PA | | 2-5 | 34-61-23 | D00353B | | B13 | | | | GDX0012 | D.. | 2 | | 150-156, 162-166 |
| 163 | 22 | PA | | 2-6 | 34-61-23 | D00353B | | B13 | | | | GDX0010 | D.. | 2 | | 157 |
| 163 | 22 | PA | | 2-7 | 34-61-23 | D00353B | | B13 | | | | GDX0013 | D.. | 2 | | 167-199 |
| 164 | 24 | PK | | 3-5 | SPARE | D00351B | | E07 | | | | D04767P | 41 | | | 050-099 |
| 164 | 24 | PK | | 3-5 | 34-12-22 | D00351B | | E07 | | | | D04767P | 41 | | | 275-299 |
| 165 | 22 | PA | | 3-8 | 22-21-21 | D05065P | | 1 | | | | D04767P | 42 | | | ALL |
| 168 | 22 | PA | | 3-10 | 27-09-14 | D05065P | | 4 | | | | D05407P | 17 | | | ALL |
| 169 | 22 | PA | | 3-8 | 34-21-21 | D05065P | | 5 | | | | D04767P | 44 | | | ALL |
| 170 | 22 | PA | | 3-8 | 34-21-21 | D05065P | | 6 | | | | D04767P | 45 | | | ALL |
| 171 | 22 | PA | | 3-8 | 34-21-21 | D05065P | | 7 | | | | D04767P | 46 | | | ALL |
| 172 | 24 | PK | | 3-2 | 34-61-25 | D05065P | | 8 | | | | D00353B | K07 | | | ALL |
| 173 | 24 | PK | | 3-9 | 34-61-25 | D05065P | | 12 | | | | TB0145Y | A155 | BJ | | ALL |
| 174 | 24 | PK | | 3-5 | 34-61-25 | TB0145Y | | A155 | BJ | | | D00353A | K13 | | | ALL |
| 175 | 22 | PA | | 3-10 | 27-09-14 | D05065P | | 13 | | | | D05407P | 6 | | | ALL |
| 176 | 24 | PK | | 3-11 | 31-51-41 | D05065P | | 14 | | | | D04819P | 52 | | | ALL |
| 177 | 24 | PK | | 4-2 | 31-31-18 | D04505P | | 47 | | | | TB0145X | B149 | BJ | | ALL |
| 178 | 24 | PK | | 4-2 | 31-31-18 | D04505P | | 55 | | | | TB0145X | A149 | BJ | | ALL |
| 179 | 22 | PA | | 4-9 | 31-31-18 | D04505P | | 49 | | | | TB0145Z | 131 | BJ | | ALL |
| 180 | 24 | PK | | 4-1 | 31-31-18 | D04505P | | 50 | | | | TB0145X | C151 | BJ | | ALL |
| 181 | 24 | PK | | 4-1 | 31-31-18 | D04505P | | 45 | | | | TB0145X | A151 | BJ | | ALL |
| 182 | 24 | PK | | 4-1 | 31-31-18 | D04505P | | 46 | | | | TB0145X | B151 | BJ | | ALL |
| 183 | 24 | PK | | 4-2 | 31-31-18 | D04505P | | 43 | | | | TB0145X | C149 | BJ | | ALL |
| 184 | 24 | PK | | 4-2 | 31-31-18 | D04505P | | 44 | | | | TB0145X | D149 | BJ | | ALL |
| 185 | 24 | PK | | 4-1 | 31-31-18 | D04505P | | 48 | | | | TB0145X | D151 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 65

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 191 | 22 | | PA | | 4-0 | 34-61-24 | D04505P | 30 | | | TB0145Y | C054 | BJ | | ALL |
| 192 | 22 | | PA | | 3-6 | 34-61-24 | D00353A | K04 | | | TB0145Y | C054 | BJ | | ALL |
| 193 | 22 | | PA | | 3-10 | 34-22-26 | D04821P | 55 | | | TB0145Y | C054 | BJ | | ALL |
| 194 | 22 | | PA | | 2-5 | 34-61-23 | D00353B | C13 | | | GDX0012 | D.. | 2 | | 275-299 |
| 195 | 24 | | PK | | 4-3 | 31-31-19 | TB0145X | A047 | BJ | | D04505P | 51 | | | 050-099, 150-199, 275-276 |
| 195 | 24 | | PK | | 3-6 | 31-31-19 | TB0145X | A083 | BJ | | D04505P | 51 | | | 277-299 |
| 196 | 24 | | PK | | 4-5 | 31-31-19 | TB0145Z | 138 | BJ | | D04505P | 52 | | | ALL |
| 197 | 24 | | PK | | 3-8 | 34-61-26 | D04505P | 39 | | | TB0145Y | C168 | BJ | | ALL |
| 198 | 22 | | PA | | 2-7 | 34-61-24 | D00353B | G11 | | | GDX0009 | D.. | 2 | | 150, 152-165, 167-199, 275-299 |
| 198 | 22 | | PA | | 2-7 | 34-61-24 | D00353B | C15 | | | GDX0009 | D.. | 2 | | 151, 166 |
| 199 | 22 | | PA | | 2-7 | 34-61-24 | D00353B | J11 | | | GDX0009 | D.. | 2 | | ALL |
| 201 | 20 | | UA | | 1-6 | 34-61-11 | GDY0011 | S.. | 2 | | TB0145X | REF | | IA | 050-099, 150-199, 275-276 |
| 201B | 24 | | PW | IA | 3-2 | 34-61-11 | D00353B | H01 | | | TB0145X | B161 | BJ | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-61-11 | D00353B | G01 | | | TB0145X | A161 | BJ | | ALL |
| 201Z | | | | IA | 0-0 | 34-61-11 | D00353B | DED | | | TB0145X | REF | | IA | 050-099, 150-199, 275-276 |
| 201Z | | | | IA | 0-0 | 34-61-11 | D00353B | DED | | | GDY0010 | S.. | 2 | | 277-299 |
| 202 | 20 | | UA | | 1-6 | 34-61-11 | D00353A | REF | | IB | GDX0012 | S.. | 2 | | ALL |
| 202B | 24 | | PW | IB | 4-2 | 34-61-11 | D00353A | B13 | | | D05713P | 25 | | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-61-11 | D00353A | A13 | | | D05713P | 24 | | | ALL |
| 202Z | | | | IB | 0-0 | 34-61-11 | D00353A | REF | | IB | D05713P | 26 | | | ALL |
| 203B | 24 | | PW | IC | 3-3 | 34-61-11 | D05713P | 19 | | | TB0145Z | 46 | BJ | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 34-61-11 | D05713P | 18 | | | TB0145Z | 45 | BJ | | ALL |
| 203Z | | | | IC | 0-0 | 34-61-11 | D05713P | 20 | | | GDY0008 | S.. | 2 | | ALL |
| 204B | 24 | | PW | ID | 6-11 | 27-32-21 | D04679P | 2 | | | TB0145Y | C063 | BJ | | 050, 150, 152-199 |
| 204B | 24 | | PW | ID | 6-11 | 27-32-21 | D04679P | 2 | | | TB0145Z | 16 | BJ | | 051-099, 151, 275-276 |
| 204B | 24 | | PW | ID | 6-8 | 27-32-21 | D04679P | 2 | | | TB0145Z | 22 | BJ | | 277-299 |
| 204R | 24 | | PW | ID | 0-0 | 27-32-21 | D04679P | 1 | | | TB0145Y | A063 | BJ | | 050, 150, 152-199 |
| 204R | 24 | | PW | ID | 0-0 | 27-32-21 | D04679P | 1 | | | TB0145Z | 15 | BJ | | 051-099, 151, 275-276 |
| 204R | 24 | | PW | ID | 0-0 | 27-32-21 | D04679P | 1 | | | TB0145Z | 21 | BJ | | 277-299 |
| 204Z | | | | ID | 0-0 | 27-32-21 | D04679P | 3 | | | GDY0009 | S.. | 2 | | 050, 150, 152-199 |
| 204Z | | | | ID | 0-0 | 27-32-21 | D04679P | 3 | | | GDY0003 | S.. | 2 | | 051-099, 151, 275-299 |
| 206 | 20 | | UA | | 1-6 | 34-61-11 | GDY0012 | S.. | 2 | | TB0145X | REF | | IF | 050-099, 150-199, 275-276 |
| 206B | 24 | | PW | IF | 3-2 | 34-61-11 | D00353A | E11 | | | TB0145X | D161 | BJ | | ALL |
| 206R | 24 | | PW | IF | 0-0 | 34-61-11 | D00353A | D11 | | | TB0145X | C161 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 66

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | | |
| 206Z | | | | IF | 0-0 | 34-61-11 | D00353A | DED | | | | | TB0145X | REF | | IF | 050-099, 150-199, 275-276 |
| 206Z | | | | IF | 0-0 | 34-61-11 | D00353A | DED | | | | | GDY0010 | S.. | 2 | | 277-299 |
| 207B | 24 | PW | IG | | 4-7 | 34-61-21 | TB0145Z | 46 | BJ | | | | D04433P | 5 | | | ALL |
| 207R | 24 | PW | IG | | 0-0 | 34-61-21 | TB0145Z | 45 | BJ | | | | D04433P | 4 | | | ALL |
| 207Z | | | | IG | 0-0 | 34-61-21 | GDY0008 | S.. | 2 | | | | D04433P | 6 | | | ALL |
| 209 | 20 | UA | | | 1-6 | 34-61-22 | D00353A | REF | | | II | | GDY0012 | S.. | 2 | | ALL |
| 209B | 24 | PW | II | | 3-2 | 34-61-22 | D04821P | 27 | | | | | D00353A | H01 | | | ALL |
| 209R | 24 | PW | II | | 0-0 | 34-61-22 | D04821P | 26 | | | | | D00353A | G01 | | | ALL |
| 209Z | | | | II | 0-0 | 34-61-22 | D04821P | 28 | | | | | D00353A | REF | | II | ALL |
| 210 | 20 | UA | | | 1-6 | 34-61-22 | D00353A | REF | | | IJ | | GDY0012 | S.. | 2 | | ALL |
| 210B | 24 | PW | IJ | | 3-2 | 34-61-22 | D04821P | 23 | | | | | D00353A | H05 | | | ALL |
| 210R | 24 | PW | IJ | | 0-0 | 34-61-22 | D04821P | 24 | | | | | D00353A | G05 | | | ALL |
| 210Z | | | | IJ | 0-0 | 34-61-22 | D04821P | 25 | | | | | D00353A | REF | | IJ | ALL |
| 212B | 24 | PW | IL | | 4-8 | 27-32-21 | D04679P | 5 | | | | | D04667P | 43 | | | ALL |
| 212R | 24 | PW | IL | | 0-0 | 27-32-21 | D04679P | 4 | | | | | D04667P | 42 | | | ALL |
| 212Z | | | | IL | 0-0 | 27-32-21 | D04679P | 6 | | | | | D04667P | 41 | | | ALL |
| 213 | 20 | UA | | | 1-6 | 34-61-23 | GDY0010 | S.. | 2 | | | | TB0145X | REF | | IM | 050-099, 275-276 |
| 213 | 20 | UA | | | 1-6 | 34-61-23 | GDY0011 | S.. | 2 | | | | TB0145X | REF | | IM | 150-199 |
| 213B | 24 | PW | IM | | 3-5 | 34-61-23 | D00353A | E07 | | | | | TB0145X | B159 | BJ | | ALL |
| 213R | 24 | PW | IM | | 0-0 | 34-61-23 | D00353A | D07 | | | | | TB0145X | A159 | BJ | | ALL |
| 213Z | | | | IM | 0-0 | 34-61-23 | D00353A | DED | | | | | TB0145X | REF | | IM | 050-099, 150-199, 275-276 |
| 213Z | | | | IM | 0-0 | 34-61-23 | D00353A | DED | | | | | GDY0010 | S.. | 2 | | 277-299 |
| 214 | 20 | UA | | | 1-6 | 34-61-23 | GDY0011 | S.. | 2 | | | | TB0145X | REF | | IN | 050-099, 150-199, 275-276 |
| 214B | 24 | PW | IN | | 3-5 | 34-61-23 | D00353A | B01 | | | | | TB0145X | B157 | BJ | | ALL |
| 214R | 24 | PW | IN | | 0-0 | 34-61-23 | D00353A | A01 | | | | | TB0145X | A157 | BJ | | ALL |
| 214Z | | | | IN | 0-0 | 34-61-23 | D00353A | DED | | | | | TB0145X | REF | | IN | 050-099, 150-199, 275-276 |
| 214Z | | | | IN | 0-0 | 34-61-23 | D00353A | DED | | | | | GDY0009 | S.. | 2 | | 277-299 |
| 215 | 20 | UA | | | 1-6 | 34-61-23 | GDY0011 | S.. | 2 | | | | TB0145X | REF | | IO | 050-099, 150-199, 275-276 |
| 215B | 24 | PW | IO | | 3-5 | 34-61-23 | D00353A | E01 | | | | | TB0145X | D157 | BJ | | ALL |
| 215R | 24 | PW | IO | | 0-0 | 34-61-23 | D00353A | D01 | | | | | TB0145X | C157 | BJ | | ALL |
| 215Z | | | | IO | 0-0 | 34-61-23 | D00353A | DED | | | | | TB0145X | REF | | IO | 050-099, 150-199, 275-276 |
| 215Z | | | | IO | 0-0 | 34-61-23 | D00353A | DED | | | | | GDY0009 | S.. | 2 | | 277-299 |
| 216B | 24 | PW | IP | | 3-6 | 34-61-22 | D00353A | E15 | | | | | TB0145X | B152 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 67

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 216R | 24 | PW | IP | 0-0 | 34-61-22 | D00353A | D15 | | | | TB0145X | A152 | BJ | | ALL |
| 216Z | | | IP | 0-0 | 34-61-22 | D00353A | DED | | | | GDY0010 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 216Z | | | IP | 0-0 | 34-61-22 | D00353A | DED | | | | GDY0009 | S.. | 2 | | 277-299 |
| 217 | 20 | UA | | 1-6 | 34-61-23 | GDX0008 | S.. | 2 | | | TB0145X | REF | | IQ | 050-099, 155-199, 275-276 |
| 217 | 20 | UA | | 1-6 | 34-61-23 | GDY0011 | S.. | 2 | | | TB0145X | REF | | IQ | 150-154 |
| 217B | 24 | PW | IQ | 3-5 | 34-61-23 | D00353A | B03 | | | | TB0145X | D159 | BJ | | ALL |
| 217R | 24 | PW | IQ | 0-0 | 34-61-23 | D00353A | A03 | | | | TB0145X | C159 | BJ | | ALL |
| 217Z | | | IQ | 0-0 | 34-61-23 | D00353A | DED | | | | TB0145X | REF | | IQ | 050-099, 150-199, 275-276 |
| 217Z | | | IQ | 0-0 | 34-61-23 | D00353A | DED | | | | GDY0010 | S.. | 2 | | 277-299 |
| 218B | 24 | PW | IR | 5-1 | 34-61-22 | D00353B | E01 | | | | TB0145Y | C013 | BJ | | 050-099, 150-199, 275-276 |
| 218B | 24 | PW | IR | 4-10 | 34-61-22 | D00353B | E01 | | | | TB0145Y | C025 | BJ | | 277-299 |
| 218R | 24 | PW | IR | 0-0 | 34-61-22 | D00353B | D01 | | | | TB0145Y | A013 | BJ | | 050-099, 150-199, 275-276 |
| 218R | 24 | PW | IR | 0-0 | 34-61-22 | D00353B | D01 | | | | TB0145Y | A025 | BJ | | 277-299 |
| 218Z | | | IR | 0-0 | 34-61-22 | D00353B | DED | | | | GDY0002 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 218Z | | | IR | 0-0 | 34-61-22 | D00353B | DED | | | | GDY0003 | S.. | 2 | | 277-299 |
| 219B | 24 | PW | IS | 5-3 | 34-61-22 | D00353B | H07 | | | | TB0145Y | C005 | BJ | | 050-099, 150-199, 275-276 |
| 219B | 24 | PW | IS | 5-3 | 34-61-22 | D00353B | H07 | | | | TB0145Y | C011 | BJ | | 277-299 |
| 219R | 24 | PW | IS | 0-0 | 34-61-22 | D00353B | G07 | | | | TB0145Y | A005 | BJ | | 050-099, 150-199, 275-276 |
| 219R | 24 | PW | IS | 0-0 | 34-61-22 | D00353B | G07 | | | | TB0145Y | A011 | BJ | | 277-299 |
| 219Z | | | IS | 0-0 | 34-61-22 | D00353B | DED | | | | GDY0001 | S.. | 2 | | ALL |
| 220B | 24 | PW | IT | 4-0 | 34-61-22 | D00353B | E05 | | | | TB0145Z | 40 | BJ | | ALL |
| 220R | 24 | PW | IT | 0-0 | 34-61-22 | D00353B | D05 | | | | TB0145Z | 39 | BJ | | ALL |
| 220Z | | | IT | 0-0 | 34-61-22 | D00353B | DED | | | | GDY0007 | S.. | 2 | | ALL |
| 221 | 20 | UA | | 0-12 | 34-61-22 | TB0145Z | REF | | IU | | GDY0011 | S.. | 2 | | 050-099, 275-276 |
| 221 | 20 | UA | | 0-12 | 34-61-22 | TB0145Z | REF | | IU | | GDY0012 | S.. | 2 | | 150-199 |
| 221B | 24 | PW | IU | 3-6 | 34-61-22 | D00353B | B03 | | | | TB0145Z | 56 | BJ | | 050-099, 150-199, 275-276 |
| 221B | 24 | PW | IU | 2-11 | 34-61-22 | D00353B | B03 | | | | TB0145Z | 78 | BJ | | 277-299 |
| 221R | 24 | PW | IU | 0-0 | 34-61-22 | D00353B | A03 | | | | TB0145Z | 55 | BJ | | 050-099, 150-199, 275-276 |
| 221R | 24 | PW | IU | 0-0 | 34-61-22 | D00353B | A03 | | | | TB0145Z | 77 | BJ | | 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 68
Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | | |
| 221Z | | | | IU | 0-0 | 34-61-22 | D00353B | DED | | | | | TB0145Z | REF | | IU | 050-099, 150-199, 275-276 |
| 221Z | | | | IU | 0-0 | 34-61-22 | D00353B | DED | | | | | GDY0012 | S.. | 2 | | 277-299 |
| 222B | 24 | | PW | IV | 3-9 | 34-61-21 | D00353A | B09 | | | | | TB0145Z | 46 | BJ | | ALL |
| 222R | 24 | | PW | IV | 0-0 | 34-61-21 | D00353A | A09 | | | | | TB0145Z | 45 | BJ | | ALL |
| 222Z | | | | IV | 0-0 | 34-61-21 | D00353A | DED | | | | | GDY0009 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 222Z | | | | IV | 0-0 | 34-61-21 | D00353A | DED | | | | | GDY0008 | S.. | 2 | | 277-299 |
| 223 | 20 | | UA | | 1-6 | 34-61-24 | D00353A | REF | | | IW | | GDY0012 | S.. | 2 | | 050-099, 150-199 |
| 223 | 20 | | UA | | 1-6 | 34-61-24 | TB0145Y | REF | | | IW | | GDY0010 | S.. | 2 | | 275-276 |
| 223B | 24 | | PW | IW | 3-2 | 34-61-24 | D00353A | H03 | | | | | D05065P | | 27 | | 050-099, 150-156, 162-166 |
| 223B | 24 | | PW | IW | 3-1 | 34-61-24 | D00353A | H03 | | | | | TB0145Y | C075 | BJ | | 157, 167-199, 275-276 |
| 223B | 24 | | PW | IW | 3-1 | 34-61-24 | D00353A | H03 | | | | | TB0145Y | C073 | BJ | | 277-299 |
| 223R | 24 | | PW | IW | 0-0 | 34-61-24 | D00353A | G03 | | | | | D05065P | | 26 | | 050-099, 150-156, 162-166 |
| 223R | 24 | | PW | IW | 0-0 | 34-61-24 | D00353A | G03 | | | | | TB0145Y | A075 | BJ | | 157, 167-199, 275-276 |
| 223R | 24 | | PW | IW | 0-0 | 34-61-24 | D00353A | G03 | | | | | TB0145Y | A073 | BJ | | 277-299 |
| 223Z | | | | IW | 0-0 | 34-61-24 | D00353A | REF | | | IW | | D05065P | | 28 | | 050-099, 150-156, 162-166 |
| 223Z | | | | IW | 0-0 | 34-61-24 | D00353A | REF | | | IW | | TB0145Y | DED | | | 157, 167-199 |
| 223Z | | | | IW | 0-0 | 34-61-24 | D00353A | DED | | | | | TB0145Y | REF | | IW | 275-276 |
| 223Z | | | | IW | 0-0 | 34-61-24 | D00353A | DED | | | | | GDY0011 | S.. | 2 | | 277-299 |
| 224 | 20 | | UA | | 1-6 | 34-61-24 | TB0145Y | REF | | | KU | | GDY0010 | S.. | 2 | | 275-276 |
| 224B | 24 | | PW | KU | 3-4 | 34-61-24 | D05065P | | | | | | TB0145Y | C075 | BJ | | 275-276 |
| 224R | 24 | | PW | KU | 0-0 | 34-61-24 | D05065P | | | | | | TB0145Y | A075 | BJ | | 275-276 |
| 224Z | | | | KU | 0-0 | 34-61-24 | D05065P | | | | | | TB0145Y | REF | | KU | 275-276 |
| 225 | 20 | | UA | | 1-6 | 34-61-24 | D00353A | REF | | | IY | | GDY0012 | S.. | 2 | | ALL |
| 225B | 24 | | PW | IY | 2-11 | 34-61-24 | D00353A | E05 | | | | | D05715J | | 17 | | ALL |
| 225R | 24 | | PW | IY | 0-0 | 34-61-24 | D00353A | D05 | | | | | D05715J | | 16 | | ALL |
| 225Z | | | | IY | 0-0 | 34-61-24 | D00353A | REF | | | IY | | D05715J | | 18 | | ALL |
| 226 | 20 | | UA | | 1-6 | 34-61-24 | D00353A | REF | | | JA | | GDY0012 | S.. | 2 | | ALL |
| 226B | 24 | | PW | JA | 3-2 | 34-61-24 | D00353A | H07 | | | | | D04821P | | 3 | | ALL |
| 226R | 24 | | PW | JA | 0-0 | 34-61-24 | D00353A | G07 | | | | | D04821P | | 2 | | ALL |
| 226Z | | | | JA | 0-0 | 34-61-24 | D00353A | REF | | | JA | | D04821P | | 4 | | ALL |
| 227 | 20 | | UA | | 1-6 | 34-61-24 | D00353A | REF | | | JB | | GDY0012 | S.. | 2 | | ALL |
| 227B | 24 | | PW | JB | 3-2 | 34-61-24 | D00353A | B05 | | | | | D04821P | | 6 | | ALL |
| 227R | 24 | | PW | JB | 0-0 | 34-61-24 | D00353A | A05 | | | | | D04821P | | 5 | | ALL |
| 227Z | | | | JB | 0-0 | 34-61-24 | D00353A | REF | | | JB | | D04821P | | 7 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 69

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 229B | 24 | | PW | JD | 3-0 | 22-33-11 | D05715J | | 26 | | D04767P | 26 | | | ALL |
| 229R | 24 | | PW | JD | 0-0 | 22-33-11 | D05715J | | 25 | | D04767P | 25 | | | ALL |
| 229Z | | | | JD | 0-0 | 22-33-11 | D05715J | | 27 | | D04767P | 28 | | | ALL |
| 230 | 20 | | UA | | 1-6 | 34-61-24 | D00353B | REF | | JE | GDX0012 | S.. | 2 | | ALL |
| 230B | 24 | | PW | JE | 3-5 | 34-61-24 | D00353B | | E03 | | D04505P | 13 | | | ALL |
| 230R | 24 | | PW | JE | 0-0 | 34-61-24 | D00353B | | D03 | | D04505P | 12 | | | ALL |
| 230Z | | | | JE | 0-0 | 34-61-24 | D00353B | REF | | JE | D04505P | 14 | | | ALL |
| 233B | 24 | | PW | JH | 3-6 | 34-61-25 | D00353B | | E07 | | TB0145Z | 58 | BJ | | 050-099, 150-199, 275-276 |
| 233B | 24 | | PW | JH | 2-11 | 34-61-25 | D00353B | | E07 | | TB0145Z | 80 | BJ | | 277-299 |
| 233R | 24 | | PW | JH | 0-0 | 34-61-25 | D00353B | | D07 | | TB0145Z | 57 | BJ | | 050-099, 150-199, 275-276 |
| 233R | 24 | | PW | JH | 0-0 | 34-61-25 | D00353B | | D07 | | TB0145Z | 79 | BJ | | 277-299 |
| 233Z | | | | JH | 0-0 | 34-61-25 | D00353B | | DED | | GDY0010 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 233Z | | | | JH | 0-0 | 34-61-25 | D00353B | | DED | | GDY0012 | S.. | 2 | | 277-299 |
| 234B | 24 | | PW | JI | 5-1 | 34-61-25 | D00353A | | H09 | | TB0145Z | 16 | BJ | | 050-099, 150-199, 275-276 |
| 234B | 24 | | PW | JI | 4-10 | 34-61-25 | D00353A | | H09 | | TB0145Z | 22 | BJ | | 277-299 |
| 234R | 24 | | PW | JI | 0-0 | 34-61-25 | D00353A | | G09 | | TB0145Z | 15 | BJ | | 050-099, 150-199, 275-276 |
| 234R | 24 | | PW | JI | 0-0 | 34-61-25 | D00353A | | G09 | | TB0145Z | 21 | BJ | | 277-299 |
| 234Z | | | | JI | 0-0 | 34-61-25 | D00353A | | DED | | GDY0003 | S.. | 2 | | ALL |
| 235B | 24 | | PW | JJ | 3-0 | 22-33-11 | D05715J | | 33 | | D04767P | 49 | | | ALL |
| 235R | 24 | | PW | JJ | 0-0 | 22-33-11 | D05715J | | 32 | | D04767P | 48 | | | ALL |
| 235Z | | | | JJ | 0-0 | 22-33-11 | D05715J | | 34 | | D04767P | 29 | | | ALL |
| 241 | 20 | | UA | | 1-6 | 22-32-11 | GDY0012 | S.. | 2 | | TB0145Y | REF | | JP | 050-099, 150-199, 275-276 |
| 241B | 24 | | PW | JP | 3-4 | 22-32-11 | D04767P | | 14 | | TB0145Y | C063 | BJ | | ALL |
| 241R | 24 | | PW | JP | 0-0 | 22-32-11 | D04767P | | 13 | | TB0145Y | A063 | BJ | | ALL |
| 241Z | | | | JP | 0-0 | 22-32-11 | D04767P | | 15 | | TB0145Y | REF | | JP | 050-099, 150-199, 275-276 |
| 241Z | | | | JP | 0-0 | 22-32-11 | D04767P | | 15 | | GDY0010 | S.. | 2 | | 277-299 |
| 242B | 24 | | PW | JQ | 4-9 | 22-41-11 | D04339P | | 3 | | TB0145Z | 58 | BJ | | 050-099, 150-199, 275-276 |
| 242B | 24 | | PW | JQ | 4-2 | 22-41-11 | D04339P | | 3 | | TB0145Z | 80 | BJ | | 277-299 |
| 242R | 24 | | PW | JQ | 0-0 | 22-41-11 | D04339P | | 2 | | TB0145Z | 57 | BJ | | 050-099, 150-199, 275-276 |
| 242R | 24 | | PW | JQ | 0-0 | 22-41-11 | D04339P | | 2 | | TB0145Z | 79 | BJ | | 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 70
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 242Z | | | | JQ | 0-0 | 22-41-11 | D04339P | | 4 | | GDY0010 | S.. | 2 | | 050-099, 150-199, 275-276 | |
| 242Z | | | | JQ | 0-0 | 22-41-11 | D04339P | | 4 | | GDY0012 | S.. | 2 | | 277-299 | |
| 243B | 24 | | PW | JR | 5-3 | 31-31-20 | D04339P | | 7 | | TB0145Y | C034 | BJ | | ALL | |
| 243R | 24 | | PW | JR | 0-0 | 31-31-20 | D04339P | | 6 | | TB0145Y | A034 | BJ | | ALL | |
| 243Z | | | | JR | 0-0 | 31-31-20 | D04339P | | 8 | | GDY0006 | S.. | 2 | | ALL | |
| 245B | 24 | | PW | JT | 4-6 | 34-22-28 | D04821P | | 9 | | TB0145Y | C133 | BJ | | ALL | |
| 245R | 24 | | PW | JT | 0-0 | 34-22-28 | D04821P | | 8 | | TB0145Y | A133 | BJ | | ALL | |
| 245Z | | | | JT | 0-0 | 34-22-28 | D04821P | | 10 | | GDY0006 | S.. | 2 | | ALL | |
| 247B | 24 | | PW | JV | 3-7 | 34-61-25 | D04767P | | 2 | | TB0145Z | | 58 | BJ | 050-099, 150-199, 275-276 | |
| 247B | 24 | | PW | JV | 3-0 | 34-61-25 | D04767P | | 2 | | TB0145Z | | 80 | BJ | 277-299 | |
| 247R | 24 | | PW | JV | 0-0 | 34-61-25 | D04767P | | 1 | | TB0145Z | | 57 | BJ | 050-099, 150-199, 275-276 | |
| 247R | 24 | | PW | JV | 0-0 | 34-61-25 | D04767P | | 1 | | TB0145Z | | 79 | BJ | 277-299 | |
| 247Z | | | | JV | 0-0 | 34-61-25 | D04767P | | 3 | | GDY0010 | S.. | 2 | | 050-099, 150-199, 275-276 | |
| 247Z | | | | JV | 0-0 | 34-61-25 | D04767P | | 3 | | GDY0012 | S.. | 2 | | 277-299 | |
| 248B | 24 | | PW | JW | 4-2 | 34-61-25 | D00353A | | B11 | | TB0145Y | C133 | BJ | | ALL | |
| 248R | 24 | | PW | JW | 0-0 | 34-61-25 | D00353A | | A11 | | TB0145Y | A133 | BJ | | ALL | |
| 248Z | | | | JW | 0-0 | 34-61-25 | D00353A | | DED | | GDY0006 | S.. | 2 | | ALL | |
| 249B | 24 | | PW | JX | 7-0 | 31-31-20 | D04339P | | 10 | | TB0145Y | C101 | BJ | | 050-099 | |
| 249B | 24 | | PW | JX | 6-11 | 31-31-20 | D04339P | | 10 | | TB0145Y | C101 | BJ | | 150-199, 275-276 | |
| 249B | 24 | | PW | JX | 6-11 | 31-31-20 | D04339P | | 10 | | TB0145Y | C107 | BJ | | 277-299 | |
| 249R | 24 | | PW | JX | 0-0 | 31-31-20 | D04339P | | 9 | | TB0145Y | A101 | BJ | | 050-099, 150-199, 275-276 | |
| 249R | 24 | | PW | JX | 0-0 | 31-31-20 | D04339P | | 9 | | TB0145Y | A107 | BJ | | 277-299 | |
| 249Z | | | | JX | 0-0 | 31-31-20 | D04339P | | 11 | | GDY0001 | S.. | 2 | | ALL | |
| 250B | 24 | | PW | JY | 3-4 | 31-35-11 | D05763P | | 17 | | TB0145Z | | 46 | BJ | ALL | |
| 250R | 24 | | PW | JY | 0-0 | 31-35-11 | D05763P | | 16 | | TB0145Z | | 45 | BJ | ALL | |
| 250Z | | | | JY | 0-0 | 31-35-11 | D05763P | | 18 | | GDY0009 | S.. | 2 | | 050-099, 150-199, 275-276 | |
| 250Z | | | | JY | 0-0 | 31-35-11 | D05763P | | 18 | | GDY0008 | S.. | 2 | | 277-299 | |
| 251B | 24 | | PW | KA | 3-4 | 34-61-13 | D05713P | | 3 | | TB0145Y | C013 | BJ | | 050-099, 150-199, 275-276 | |
| 251B | 24 | | PW | KA | 3-1 | 34-61-13 | D05713P | | 3 | | TB0145Y | C025 | BJ | | 277-299 | |
| 251R | 24 | | PW | KA | 0-0 | 34-61-13 | D05713P | | 2 | | TB0145Y | A013 | BJ | | 050-099, 150-199, 275-276 | |
| 251R | 24 | | PW | KA | 0-0 | 34-61-13 | D05713P | | 2 | | TB0145Y | A025 | BJ | | 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 71

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 251Z | | | | KA | 0-0 | 34-61-13 | D05713P | | 4 | | GDY0002 | S.. | 2 | | | 050-099, 150-199, 275-276 |
| 251Z | | | | KA | 0-0 | 34-61-13 | D05713P | | 4 | | GDY0003 | S.. | 2 | | | 277-299 |
| 252B | 24 | | PW | KB | 3-7 | 34-61-13 | D05713P | | 6 | | TB0145Y | C005 | BJ | | | 050-099, 150-199, 275-276 |
| 252B | 24 | | PW | KB | 3-6 | 34-61-13 | D05713P | | 6 | | TB0145Y | C011 | BJ | | | 277-299 |
| 252R | 24 | | PW | KB | 0-0 | 34-61-13 | D05713P | | 5 | | TB0145Y | A005 | BJ | | | 050-099, 150-199, 275-276 |
| 252R | 24 | | PW | KB | 0-0 | 34-61-13 | D05713P | | 5 | | TB0145Y | A011 | BJ | | | 277-299 |
| 252Z | | | | KB | 0-0 | 34-61-13 | D05713P | | 7 | | GDY0001 | S.. | 2 | | | ALL |
| 253B | 24 | | PW | KC | 3-1 | 34-61-13 | D05713P | | 9 | | TB0145Z | 40 | BJ | | | ALL |
| 253R | 24 | | PW | KC | 0-0 | 34-61-13 | D05713P | | 8 | | TB0145Z | 39 | BJ | | | ALL |
| 253Z | | | | KC | 0-0 | 34-61-13 | D05713P | | 10 | | GDY0007 | S.. | 2 | | | ALL |
| 254B | 24 | | PW | KD | 3-6 | 34-61-13 | D05713P | | 13 | | TB0145Z | 56 | BJ | | | 050-099, 150-199, 275-276 |
| 254B | 24 | | PW | KD | 4-1 | 34-61-13 | D05713P | | 13 | | TB0145Z | 78 | BJ | | | 277-299 |
| 254R | 24 | | PW | KD | 0-0 | 34-61-13 | D05713P | | 12 | | TB0145Z | 55 | BJ | | | 050-099, 150-199, 275-276 |
| 254R | 24 | | PW | KD | 0-0 | 34-61-13 | D05713P | | 12 | | TB0145Z | 77 | BJ | | | 277-299 |
| 254Z | | | | KD | 0-0 | 34-61-13 | D05713P | | 14 | | GDY0010 | S.. | 2 | | | 050-099, 150-199, 275-276 |
| 254Z | | | | KD | 0-0 | 34-61-13 | D05713P | | 14 | | GDY0012 | S.. | 2 | | | 277-299 |
| 256B | 22 | | PB | KF | 3-11 | 31-51-43 | D05407P | | 11 | | D04819P | 47 | | | | ALL |
| 256R | 22 | | PB | KF | 0-0 | 31-51-43 | D05407P | | 10 | | D04819P | 46 | | | | ALL |
| 259B | 24 | | PW | KI | 3-7 | 34-61-22 | D04767P | | 11 | | TB0145Z | 56 | BJ | | | 050-099, 150-199, 275-276 |
| 259B | 24 | | PW | KI | 3-0 | 34-61-22 | D04767P | | 11 | | TB0145Z | 78 | BJ | | | 277-299 |
| 259R | 24 | | PW | KI | 0-0 | 34-61-22 | D04767P | | 10 | | TB0145Z | 55 | BJ | | | 050-099, 150-199, 275-276 |
| 259R | 24 | | PW | KI | 0-0 | 34-61-22 | D04767P | | 10 | | TB0145Z | 77 | BJ | | | 277-299 |
| 259Z | | | | KI | 0-0 | 34-61-22 | D04767P | | 12 | | GDY0010 | S.. | 2 | | | 050-099, 150-199, 275-276 |
| 259Z | | | | KI | 0-0 | 34-61-22 | D04767P | | 12 | | GDY0012 | S.. | 2 | | | 277-299 |
| 260B | 24 | | PW | KJ | 2-11 | 31-35-13 | D05713P | | 36 | | TB0145Y | C133 | BJ | | | ALL |
| 260R | 24 | | PW | KJ | 0-0 | 31-35-13 | D05713P | | 35 | | TB0145Y | A133 | BJ | | | ALL |
| 260Z | | | | KJ | 0-0 | 31-35-13 | D05713P | | 37 | | GDY0006 | S.. | 2 | | | ALL |
| 261B | 24 | | PW | KK | 3-10 | 34-51-21 | D00357B | | B04 | | TB0145Y | C013 | BJ | | | 050-099, 150-199, 275-276 |
| 261B | 24 | | PW | KK | 3-8 | 34-51-21 | D00357B | | B04 | | TB0145Y | C025 | BJ | | | 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 72
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 261R | 24 | PW | KK | 0-0 | 34-51-21 | D00357B | A04 | | | | TB0145Y | A013 | BJ | | 050-099, 150-199, 275-276 | |
| 261R | 24 | PW | KK | 0-0 | 34-51-21 | D00357B | A04 | | | | TB0145Y | A025 | BJ | | 277-299 | |
| 261Z | | | KK | 0-0 | 34-51-21 | D00357B | DED | | | | GDY0003 | S.. | 2 | | ALL | |
| 262 | 20 | UA | | 1-6 | 34-51-21 | D00357B | REF | | | KL | GDY0005 | S.. | 2 | | ALL | |
| 262B | 24 | PW | KL | 5-5 | 34-51-21 | D00357B | C11 | | | | D04377P | | 31 | | ALL | |
| 262R | 24 | PW | KL | 0-0 | 34-51-21 | D00357B | B11 | | | | D04377P | | 18 | | ALL | |
| 262Z | | | KL | 0-0 | 34-51-21 | D00357B | REF | | | KL | D04377P | | 30 | | ALL | |
| 263B | 22 | PB | KM | 5-5 | 34-51-21 | D00357B | D15 | | | | D04377P | | 2 | | ALL | |
| 263R | 22 | PB | KM | 0-0 | 34-51-21 | D00357B | C15 | | | | D04377P | | 1 | | ALL | |
| 264 | 20 | UA | | 1-6 | 34-51-21 | GDY0003 | S.. | 2 | | | TB0145Z | REF | | KN | 277-299 | |
| 264B | 24 | PW | KN | 4-1 | 34-51-21 | D00357B | C09 | | | | TB0145Y | C007 | BJ | | 050-099, 150-199 | |
| 264B | 24 | PW | KN | 4-0 | 34-51-21 | D00357B | C09 | | | | TB0145Z | 182 | BJ | | 275-276 | |
| 264B | 24 | PW | KN | 3-8 | 34-51-21 | D00357B | C09 | | | | TB0145Z | 24 | BJ | | 277-299 | |
| 264R | 24 | PW | KN | 0-0 | 34-51-21 | D00357B | B09 | | | | TB0145Y | A007 | BJ | | 050-099, 150-199 | |
| 264R | 24 | PW | KN | 0-0 | 34-51-21 | D00357B | B09 | | | | TB0145Z | 181 | BJ | | 275-276 | |
| 264R | 24 | PW | KN | 0-0 | 34-51-21 | D00357B | B09 | | | | TB0145Z | 23 | BJ | | 277-299 | |
| 264Z | | | KN | 0-0 | 34-51-21 | D00357B | DED | | | | GDY0001 | S.. | 2 | | 050-099, 150-199 | |
| 264Z | | | KN | 0-0 | 34-51-21 | D00357B | DED | | | | GDY0013 | S.. | 2 | | 275-276 | |
| 264Z | | | KN | 0-0 | 34-51-21 | D00357B | DED | | | | TB0145Z | REF | | KN | 277-299 | |
| 265B | 24 | PL | KO | 4-9 | 23-51-12 | D00357B | C07 | | | | D04811P | 9 | | | ALL | |
| 265R | 24 | PL | KO | 0-0 | 23-51-12 | D00357B | B07 | | | | D04811P | 8 | | | ALL | |
| 266B | 24 | PW | KP | 3-4 | 31-35-13 | D05713P | 39 | | | | TB0145Z | 16 | BJ | | 050-099, 150-199, 275-276 | |
| 266B | 24 | PW | KP | 3-1 | 31-35-13 | D05713P | 39 | | | | TB0145Z | 22 | BJ | | 277-299 | |
| 266R | 24 | PW | KP | 0-0 | 31-35-13 | D05713P | 38 | | | | TB0145Z | 15 | BJ | | 050-099, 150-199, 275-276 | |
| 266R | 24 | PW | KP | 0-0 | 31-35-13 | D05713P | 38 | | | | TB0145Z | 21 | BJ | | 277-299 | |
| 266Z | | | KP | 0-0 | 31-35-13 | D05713P | 40 | | | | GDY0003 | S.. | 2 | | ALL | |
| 267B | 24 | PW | KQ | 2-11 | 34-51-21 | D00357B | C13 | | | | TB0145Y | C135 | BJ | | ALL | |
| 267R | 24 | PW | KQ | 0-0 | 34-51-21 | D00357B | B13 | | | | TB0145Y | A135 | BJ | | ALL | |
| 267Z | | | KQ | 0-0 | 34-51-21 | D00357B | DED | | | | GDY0006 | S.. | 2 | | ALL | |
| 268B | 24 | PW | KR | 4-4 | 34-51-21 | D04377P | 22 | | | | D04821P | 33 | | | ALL | |
| 268R | 24 | PW | KR | 0-0 | 34-51-21 | D04377P | 10 | | | | D04821P | 32 | | | ALL | |
| 268Z | | | KR | 0-0 | 34-51-21 | D04377P | 23 | | | | D04821P | 34 | | | ALL | |
| 269B | 24 | PW | KS | 6-10 | 34-51-21 | TB0145Y | C013 | BJ | | | D04377P | 21 | | | 050-099, 150-199, 275-276 | |
| 269B | 24 | PW | KS | 6-7 | 34-51-21 | TB0145Y | C025 | BJ | | | D04377P | 21 | | | 277-299 | |

WIRE LIST D280T132

91-21-11
Section W0140
Page 73
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 269R | 24 | PW | KS | | 0-0 | 34-51-21 | TB0145Y | A013 | BJ | | D04377P | 8 | | | 050-099, 150-199, 275-276 |
| 269R | 24 | PW | KS | | 0-0 | 34-51-21 | TB0145Y | A025 | BJ | | D04377P | 8 | | | 277-299 |
| 269Z | | | KS | | 0-0 | 34-51-21 | GDY0003 | S.. | 2 | | D04377P | 20 | | | ALL |
| 270 | 20 | UA | | | 1-6 | 31-36-11 | D00353B | REF | | KT | GDX0012 | S.. | 2 | | ALL |
| 270B | 24 | PW | KT | | 2-9 | 31-36-11 | D00353B | H05 | | | D05763P | 41 | | | ALL |
| 270R | 24 | PW | KT | | 0-0 | 31-36-11 | D00353B | G05 | | | D05763P | 40 | | | ALL |
| 270Z | | | KT | | 0-0 | 31-36-11 | D00353B | REF | | KT | D05763P | 42 | | | ALL |
| 271 | 20 | UA | | | 1-6 | 34-61-24 | TB0145Y | REF | | KU | GDX0010 | S.. | 2 | | 157, 167-199 |
| 271B | 24 | PW | KU | | 3-4 | 34-61-24 | D05065P | 27 | | | TB0145Y | C075 | BJ | | 157, 167-199 |
| 271B | 24 | PW | KU | | 3-4 | 34-61-24 | D05065P | 27 | | | TB0145Y | C073 | BJ | | 277-299 |
| 271R | 24 | PW | KU | | 0-0 | 34-61-24 | D05065P | 26 | | | TB0145Y | A075 | BJ | | 157, 167-199 |
| 271R | 24 | PW | KU | | 0-0 | 34-61-24 | D05065P | 26 | | | TB0145Y | A073 | BJ | | 277-299 |
| 271Z | | | KU | | 0-0 | 34-61-24 | D05065P | 28 | | | TB0145Y | REF | | KU | 157, 167-199 |
| 271Z | | | KU | | 0-0 | 34-61-24 | D05065P | 28 | | | GDY0011 | S.. | 2 | | 277-299 |
| 273B | 24 | PW | KW | | 4-0 | 32-42-11 | D04767P | 34 | | | D04667P | 25 | | | ALL |
| 273R | 24 | PW | KW | | 0-0 | 32-42-11 | D04767P | 33 | | | D04667P | 24 | | | ALL |
| 273Z | | | KW | | 0-0 | 32-42-11 | D04767P | 35 | | | D04667P | 26 | | | ALL |
| 275 | 20 | UA | | | 1-6 | 34-53-21 | D00359A | REF | | KY | GDX0003 | S.. | 2 | | ALL |
| 275B | 24 | PW | KY | | 6-1 | 34-53-21 | D00359A | F07 | | | D04697P | 11 | | | ALL |
| 275R | 24 | PW | KY | | 0-0 | 34-53-21 | D00359A | E07 | | | D04697P | 10 | | | ALL |
| 275Z | | | KY | | 0-0 | 34-53-21 | D00359A | REF | | KY | D04697P | 12 | | | ALL |
| 276 | 20 | UA | | | 1-6 | SPARE | D00359B | REF | | LA | GDX0003 | S.. | # | | 150-154 |
| 276B | 24 | PW | LA | | 5-3 | SPARE | D00359B | CAP | Y | | D04505P | 36 | | | 150-154 |
| 276R | 24 | PW | LA | | 0-0 | SPARE | D00359B | CAP | Y | | D04505P | 35 | | | 150-154 |
| 276Z | | | LA | | 0-0 | SPARE | D00359B | REF | | LA | D04505P | 37 | | | 150-154 |
| 277 | 20 | UA | | | 1-6 | SPARE | D00359B | REF | | LB | GDX0003 | S.. | # | | 150-154 |
| 277B | 24 | PW | LB | | 5-3 | SPARE | D00359B | CAP | Y | | D04505P | 22 | | | 150-154 |
| 277R | 24 | PW | LB | | 0-0 | SPARE | D00359B | CAP | Y | | D04505P | 21 | | | 150-154 |
| 277Z | | | LB | | 0-0 | SPARE | D00359B | REF | | LB | D04505P | 23 | | | 150-154 |
| 278B | 24 | PW | LC | | 4-0 | 34-53-21 | D00359A | J07 | | | TB0145Z | 52 | BJ | | ALL |
| 278R | 24 | PW | LC | | 0-0 | 34-53-21 | D00359A | H07 | | | TB0145Z | 51 | BJ | | ALL |
| 278Z | | | LC | | 0-0 | 34-53-21 | D00359A | DED | | | GDY0008 | S.. | 2 | | 050-099, 155-199 |
| 278Z | | | LC | | 0-0 | 34-53-21 | D00359A | DED | | | GDY0010 | S.. | 2 | | 150-154, 275-276 |
| 278Z | | | LC | | 0-0 | 34-53-21 | D00359A | DED | | | GDY0009 | S.. | 2 | | 277-299 |
| 279 | 20 | UA | | | 1-6 | 34-53-21 | D00359B | REF | | LD | GDX0003 | S.. | 2 | | ALL |
| 279B | 24 | PW | LD | | 3-0 | 34-53-21 | D00359B | B05 | | | D05713P | 21 | | | ALL |
| 279R | 24 | PW | LD | | 0-0 | 34-53-21 | D00359B | A05 | | | D05713P | 22 | | | ALL |
| 279Z | | | LD | | 0-0 | 34-53-21 | D00359B | REF | | LD | D05713P | 23 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0140
 Page 74
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 280B | 24 | PW | LE | 2-8 | 22-14-21 | D04505P | | 34 | | | | D04819P | 19 | | | 050-099, 280-299 |
| 280B | 24 | PW | LE | 3-2 | 22-14-21 | D04505P | | 34 | | | | D04819P | 19 | | | 150-199, 275-278 |
| 280R | 24 | PW | LE | 0-0 | 22-14-21 | D04505P | | 33 | | | | D04819P | 18 | | | ALL |
| 280Z | | | LE | 0-0 | 22-14-21 | D04505P | | 38 | | | | D04819P | 20 | | | ALL |
| 281 | 20 | UA | | 1-6 | 34-55-21 | GDX0006 | | S.. | 2 | | | TB0145Y | REF | | LF | 050-099, 152-156, 162-166 |
| 281 | 20 | UA | | 1-6 | 34-55-21 | GDY0013 | | S.. | 2 | | | TB0145Y | REF | | LF | 150-151 |
| 281 | 20 | UA | | 1-6 | 34-55-21 | GDX0011 | | S.. | 2 | | | TB0145Z | REF | | LF | 157, 167-199 |
| 281 | 20 | UA | | 1-6 | 34-55-21 | TB0145Z | | REF | | LF | | GDX0011 | S.. | 2 | | 275-276 |
| 281 | 20 | UA | | 1-6 | 34-55-21 | TB0145Z | | REF | | LF | | GDX0003 | S.. | 2 | | 277-299 |
| 281B | 24 | PW | LF | 4-2 | 34-55-21 | D00361B | | H03 | | | | TB0145Y | C033 | BJ | | 050-099, 150-156, 162-166 |
| 281B | 24 | PW | LF | 5-1 | 34-55-21 | D00361B | | H03 | | | | TB0145Z | 182 | BJ | | 157, 167-199 |
| 281B | 24 | PW | LF | 5-1 | 34-55-21 | D00361B | | H03 | | | | TB0145Z | 184 | BJ | | 275-276 |
| 281B | 24 | PW | LF | 3-4 | 34-55-21 | D00361B | | H03 | | | | TB0145Z | 126 | BJ | | 277-299 |
| 281R | 24 | PW | LF | 0-0 | 34-55-21 | D00361B | | G03 | | | | TB0145Y | A033 | BJ | | 050-099, 150-156, 162-166 |
| 281R | 24 | PW | LF | 0-0 | 34-55-21 | D00361B | | G03 | | | | TB0145Z | 181 | BJ | | 157, 167-199 |
| 281R | 24 | PW | LF | 0-0 | 34-55-21 | D00361B | | G03 | | | | TB0145Z | 183 | BJ | | 275-276 |
| 281R | 24 | PW | LF | 0-0 | 34-55-21 | D00361B | | G03 | | | | TB0145Z | 125 | BJ | | 277-299 |
| 281Z | | | LF | 0-0 | 34-55-21 | D00361B | | DED | | | | TB0145Y | REF | | LF | 050-099, 150-156, 162-166 |
| 281Z | | | LF | 0-0 | 34-55-21 | D00361B | | DED | | | | TB0145Z | REF | | LF | 157, 167-199, 275-299 |
| 284 | 20 | UA | | 1-6 | 34-22-29 | GDX0006 | | S.. | 2 | | | TB0145Y | REF | | LI | 050-099, 152-156, 162-166 |
| 284 | 20 | UA | | 1-6 | 34-22-29 | GDY0013 | | S.. | 2 | | | TB0145Y | REF | | LI | 150-151 |
| 284 | 20 | UA | | 1-6 | 34-22-29 | GDX0011 | | S.. | 2 | | | TB0145Z | REF | | LI | 157, 167-199, 275-276 |
| 284 | 20 | UA | | 1-6 | 34-22-29 | GDX0003 | | S.. | 2 | | | TB0145Z | REF | | LI | 277-299 |
| 284B | 24 | PW | LI | 4-4 | 34-22-29 | D04821P | | 21 | | | | TB0145Y | C033 | BJ | | 050-099, 150-156, 162-166 |
| 284B | 24 | PW | LI | 3-2 | 34-22-29 | D04821P | | 21 | | | | TB0145Z | 182 | BJ | | 157, 167-199 |
| 284B | 24 | PW | LI | 3-2 | 34-22-29 | D04821P | | 21 | | | | TB0145Z | 184 | BJ | | 275-276 |
| 284B | 24 | PW | LI | 5-1 | 34-22-29 | D04821P | | 21 | | | | TB0145Z | 126 | BJ | | 277-299 |
| 284R | 24 | PW | LI | 0-0 | 34-22-29 | D04821P | | 20 | | | | TB0145Y | A033 | BJ | | 050-099, 150-156, 162-166 |
| 284R | 24 | PW | LI | 0-0 | 34-22-29 | D04821P | | 20 | | | | TB0145Z | 181 | BJ | | 157, 167-199 |
| 284R | 24 | PW | LI | 0-0 | 34-22-29 | D04821P | | 20 | | | | TB0145Z | 183 | BJ | | 275-276 |
| 284R | 24 | PW | LI | 0-0 | 34-22-29 | D04821P | | 20 | | | | TB0145Z | 125 | BJ | | 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 75

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | | |
| 284Z | | | | LI | 0-0 | 34-22-29 | D04821P | | 22 | | | | TB0145Y | REF | | LI | 050-099, 150-156, 162-166 |
| 284Z | | | | LI | 0-0 | 34-22-29 | D04821P | | 22 | | | | TB0145Z | REF | | LI | 157, 167-199, 275-299 |
| 285B | 24 | PW | LJ | | 4-3 | 34-22-29 | D04821P | | 18 | | | | TB0145Y | C135 | BJ | | ALL |
| 285R | 24 | PW | LJ | | 0-0 | 34-22-29 | D04821P | | 17 | | | | TB0145Y | A135 | BJ | | ALL |
| 285Z | | | | LJ | 0-0 | 34-22-29 | D04821P | | 19 | | | | GDY0006 | S.. | 2 | | ALL |
| 286B | 24 | PW | LK | | 4-4 | 23-22-11 | D04811P | | 39 | | | | TB0145Z | 46 | BJ | | ALL |
| 286R | 24 | PW | LK | | 0-0 | 23-22-11 | D04811P | | 38 | | | | TB0145Z | 45 | BJ | | ALL |
| 286Z | | | | LK | 0-0 | 23-22-11 | D04811P | | 40 | | | | GDY0009 | S.. | 2 | | 050-099, 150-199, 275-276, 280-299 |
| 286Z | | | | LK | 0-0 | 23-22-11 | D04811P | | 40 | | | | GDY0008 | S.. | 2 | | 277-278 |
| 287B | 24 | PW | LL | | 4-1 | 23-22-11 | D04433P | | 20 | | | | D04811P | 23 | | | ALL |
| 287R | 24 | PW | LL | | 0-0 | 23-22-11 | D04433P | | 19 | | | | D04811P | 22 | | | ALL |
| 287Z | | | | LL | 0-0 | 23-22-11 | D04433P | | 21 | | | | D04811P | 41 | | | ALL |
| 288 | 20 | UA | | | 1-6 | 34-61-24 | TB0145Y | | REF | | LM | | GDY0006 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 288B | 24 | PW | LM | | 3-9 | 34-61-24 | D00353B | | E09 | | | | TB0145Y | C043 | BJ | | ALL |
| 288R | 24 | PW | LM | | 0-0 | 34-61-24 | D00353B | | D09 | | | | TB0145Y | A043 | BJ | | ALL |
| 288Z | | | | LM | 0-0 | 34-61-24 | D00353B | | DED | | | | TB0145Y | REF | | LM | 050-099, 152-199, 275-299 |
| 288Z | | | | LM | 0-0 | 34-61-24 | D00353B | | DED | | | | GDY0008 | S.. | 2 | | 150-151 |
| 289B | 24 | PW | LN | | 3-2 | 31-31-20 | D05713P | | 45 | | | | TB0145X | B145 | BJ | | ALL |
| 289R | 24 | PW | LN | | 0-0 | 31-31-20 | D05713P | | 44 | | | | TB0145X | A145 | BJ | | ALL |
| 289Z | | | | LN | 0-0 | 31-31-20 | D05713P | | 46 | | | | GDY0009 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 289Z | | | | LN | 0-0 | 31-31-20 | D05713P | | 46 | | | | GDY0008 | S.. | 2 | | 277-299 |
| 290 | 20 | UA | | | 1-6 | 34-55-21 | D00361B | | REF | | LO | | GDY0001 | S.. | 2 | | ALL |
| 290B | 24 | PW | LO | | 7-1 | 34-55-21 | D00361B | | E03 | | | | D04377P | 29 | | | ALL |
| 290R | 24 | PW | LO | | 0-0 | 34-55-21 | D00361B | | D03 | | | | D04377P | 16 | | | ALL |
| 290Z | | | | LO | 0-0 | 34-55-21 | D00361B | | REF | | LO | | D04377P | 28 | | | ALL |
| 291 | 20 | UA | | | 1-6 | 34-55-21 | GDY0003 | | S.. | 2 | | | TB0145Z | REF | | LP | 277-299 |
| 291B | 24 | PW | LP | | 3-1 | 34-55-21 | D00361B | | B03 | | | | TB0145Y | C007 | BJ | | 050-099, 150-199 |
| 291B | 24 | PW | LP | | 5-1 | 34-55-21 | D00361B | | B03 | | | | TB0145Z | 182 | BJ | | 275-276 |
| 291B | 24 | PW | LP | | 3-4 | 34-55-21 | D00361B | | B03 | | | | TB0145Z | 24 | BJ | | 277-299 |
| 291R | 24 | PW | LP | | 0-0 | 34-55-21 | D00361B | | A03 | | | | TB0145Y | A007 | BJ | | 050-099, 150-199 |
| 291R | 24 | PW | LP | | 0-0 | 34-55-21 | D00361B | | A03 | | | | TB0145Z | 181 | BJ | | 275-276 |
| 291R | 24 | PW | LP | | 0-0 | 34-55-21 | D00361B | | A03 | | | | TB0145Z | 23 | BJ | | 277-299 |
| 291Z | | | | LP | 0-0 | 34-55-21 | D00361B | | DED | | | | GDY0002 | S.. | 2 | | 050-099, 150-199 |
| 291Z | | | | LP | 0-0 | 34-55-21 | D00361B | | DED | | | | GDY0011 | S.. | 2 | | 275-276 |

WIRE LIST

D280T132

91-21-11
Section W0140
Page 76
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | | |
| 291Z | | | LP | 0-0 | 34-55-21 | D00361B | | DED | | | | | TB0145Z | REF | | LP | 277-299 |
| 292B | 24 | PW | LQ | 3-1 | 34-61-22 | D00361B | | H01 | | | | | TB0145Y | C005 | BJ | | 050-099, 150-199, 275-276 |
| 292B | 24 | PW | LQ | 3-1 | 34-61-22 | D00361B | | H01 | | | | | TB0145Y | C011 | BJ | | 277-299 |
| 292R | 24 | PW | LQ | 0-0 | 34-61-22 | D00361B | | G01 | | | | | TB0145Y | A005 | BJ | | 050-099, 150-199, 275-276 |
| 292R | 24 | PW | LQ | 0-0 | 34-61-22 | D00361B | | G01 | | | | | TB0145Y | A011 | BJ | | 277-299 |
| 292Z | | | LQ | 0-0 | 34-61-22 | D00361B | | DED | | | | | GDY0001 | S.. | 2 | | ALL |
| 293B | 24 | PL | LR | 3-1 | 23-51-12 | D00361B | | B01 | | | | | TB0145X | D001 | BJ | | 050-099, 150-199, 275-276 |
| 293B | 24 | PL | LR | 3-1 | 23-51-12 | D00361B | | B01 | | | | | TB0145X | D007 | BJ | | 277-299 |
| 293R | 24 | PL | LR | 0-0 | 23-51-12 | D00361B | | A01 | | | | | TB0145X | C001 | BJ | | 050-099, 150-199, 275-276 |
| 293R | 24 | PL | LR | 0-0 | 23-51-12 | D00361B | | A01 | | | | | TB0145X | C007 | BJ | | 277-299 |
| 295 | 20 | UA | | 1-6 | 34-61-25 | GDY0011 | | S.. | 2 | | | | TB0145Z | REF | | LT | 050-099, 150-199, 275-276 |
| 295B | 24 | PW | LT | 4-4 | 34-61-25 | D05439P | | 12 | | | | | TB0145Z | 58 | BJ | | 050-099, 150-199, 275-276 |
| 295B | 24 | PW | LT | 3-10 | 34-61-25 | D05439P | | 12 | | | | | TB0145Z | 80 | BJ | | 277-299 |
| 295R | 24 | PW | LT | 0-0 | 34-61-25 | D05439P | | 13 | | | | | TB0145Z | 57 | BJ | | 050-099, 150-199, 275-276 |
| 295R | 24 | PW | LT | 0-0 | 34-61-25 | D05439P | | 13 | | | | | TB0145Z | 79 | BJ | | 277-299 |
| 295Z | | | LT | 0-0 | 34-61-25 | D05439P | | 14 | | | | | TB0145Z | REF | | LT | 050-099, 150-199, 275-276 |
| 295Z | | | LT | 0-0 | 34-61-25 | D05439P | | 14 | | | | | GDY0012 | S.. | 2 | | 277-299 |
| 296 | 20 | UA | | 1-6 | 34-61-25 | GDX0003 | | S.. | 2 | | | | TB0145Z | REF | | LU | 277-299 |
| 296B | 24 | PW | LU | 6-8 | 34-61-25 | D05439P | | 15 | | | | | TB0145Y | C007 | BJ | | 050-099, 150-199 |
| 296B | 24 | PW | LU | 3-9 | 34-61-25 | D05439P | | 15 | | | | | TB0145Z | 182 | BJ | | 275-276 |
| 296B | 24 | PW | LU | 6-2 | 34-61-25 | D05439P | | 15 | | | | | TB0145Z | 24 | BJ | | 277-299 |
| 296R | 24 | PW | LU | 0-0 | 34-61-25 | D05439P | | 16 | | | | | TB0145Y | A007 | BJ | | 050-099, 150-199 |
| 296R | 24 | PW | LU | 0-0 | 34-61-25 | D05439P | | 16 | | | | | TB0145Z | 181 | BJ | | 275-276 |
| 296R | 24 | PW | LU | 0-0 | 34-61-25 | D05439P | | 16 | | | | | TB0145Z | 23 | BJ | | 277-299 |
| 296Z | | | LU | 0-0 | 34-61-25 | D05439P | | 20 | | | | | GDY0002 | S.. | 2 | | 050-099, 150-199 |
| 296Z | | | LU | 0-0 | 34-61-25 | D05439P | | 20 | | | | | GDY0012 | S.. | 2 | | 275-276 |
| 296Z | | | LU | 0-0 | 34-61-25 | D05439P | | 20 | | | | | TB0145Z | REF | | LU | 277-299 |
| 297B | 24 | PW | LV | 3-7 | 34-61-25 | D05439P | | 3 | | | | | D05763P | 2 | | | ALL |
| 297R | 24 | PW | LV | 0-0 | 34-61-25 | D05439P | | 4 | | | | | D05763P | 1 | | | ALL |
| 297Z | | | LV | 0-0 | 34-61-25 | D05439P | | 5 | | | | | D05763P | 3 | | | ALL |
| 299 | 20 | UA | | 1-6 | 34-61-21 | D00353A | | REF | | | | | GDX0012 | S.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 77

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 299 | 20 | | UA | | 2-5 | 34-61-21 | D00353A | | REF | | LX | GDX0012 | S.. | 2 | | 150-199, 275-299 |
| 299B | 24 | | PW | LX | 2-10 | 34-61-21 | D00353A | | E13 | | | TB0145Y | C179 | BJ | | ALL |
| 299R | 24 | | PW | LX | 0-0 | 34-61-21 | D00353A | | D13 | | | TB0145Y | A179 | BJ | | ALL |
| 299Z | | | | LX | 0-0 | 34-61-21 | D00353A | | REF | | LX | TB0145Y | DED | | | ALL |
| 301B | 24 | | PM | MA | 7-1 | 23-51-12 | D04377P | | 25 | | | TB0145X | B001 | BJ | | 050-099, 150-199, 275-276 |
| 301B | 24 | | PM | MA | 7-1 | 23-51-12 | D04377P | | 25 | | | TB0145X | B007 | BJ | | 277-299 |
| 301R | 24 | | PM | MA | 0-0 | 23-51-12 | D04377P | | 24 | | | TB0145X | A001 | BJ | | 050-099, 150-199, 275-276 |
| 301R | 24 | | PM | MA | 0-0 | 23-51-12 | D04377P | | 24 | | | TB0145X | A007 | BJ | | 277-299 |
| 301Y | 24 | | PM | MA | 0-0 | 23-51-12 | D04377P | | 12 | | | TB0145X | C001 | BJ | | 050-099, 150-199, 275-276 |
| 301Y | 24 | | PM | MA | 0-0 | 23-51-12 | D04377P | | 12 | | | TB0145X | C007 | BJ | | 277-299 |
| 302B | 24 | | PM | MB | 6-4 | 23-51-12 | D04811P | | 6 | | | TB0145X | B001 | BJ | | 050-099, 150-199, 275-276 |
| 302B | 24 | | PM | MB | 6-4 | 23-51-12 | D04811P | | 6 | | | TB0145X | B007 | BJ | | 277-299 |
| 302R | 24 | | PM | MB | 0-0 | 23-51-12 | D04811P | | 5 | | | TB0145X | A001 | BJ | | 050-099, 150-199, 275-276 |
| 302R | 24 | | PM | MB | 0-0 | 23-51-12 | D04811P | | 5 | | | TB0145X | A007 | BJ | | 277-299 |
| 302Y | 24 | | PM | MB | 0-0 | 23-51-12 | D04811P | | 7 | | | TB0145X | D001 | BJ | | 050-099, 150-199, 275-276 |
| 302Y | 24 | | PM | MB | 0-0 | 23-51-12 | D04811P | | 7 | | | TB0145X | D007 | BJ | | 277-299 |
| 371B | 24 | | PM | OU | 2-11 | 34-12-21 | D00351B | | J02 | | | D04317P | 7 | | | ALL |
| 371R | 24 | | PM | OU | 0-0 | 34-12-21 | D00351B | | H02 | | | D04317P | 6 | | | ALL |
| 371Y | 24 | | PM | OU | 0-0 | 34-12-21 | D00351B | | K02 | | | D04317P | 8 | | | ALL |
| 374B | 24 | | PM | OX | 2-11 | 34-12-21 | D04317P | | 2 | | | D00351B | J04 | | | ALL |
| 374R | 24 | | PM | OX | 0-0 | 34-12-21 | D04317P | | 1 | | | D00351B | H04 | | | ALL |
| 374Y | 24 | | PM | OX | 0-0 | 34-12-21 | D04317P | | 3 | | | D00351B | K04 | | | ALL |
| 375B | 24 | | PM | OY | 4-2 | 34-12-21 | TB0145Y | | C053 | BJ | | D00351B | J11 | | | ALL |
| 375R | 24 | | PM | OY | 0-0 | 34-12-21 | TB0145Y | | A053 | BJ | | D00351B | H11 | | | ALL |
| 375Y | 24 | | PM | OY | 0-0 | 34-12-21 | TB0145Y | | A054 | BJ | | D00351B | K11 | | | ALL |
| 376B | 24 | | PM | PA | 3-7 | 34-12-21 | TB0145X | | B169 | BJ | | D00351B | J10 | | | ALL |
| 376R | 24 | | PM | PA | 0-0 | 34-12-21 | TB0145X | | A169 | BJ | | D00351B | H10 | | | ALL |
| 376Y | 24 | | PM | PA | 0-0 | 34-12-21 | TB0145X | | C169 | BJ | | D00351B | K10 | | | ALL |
| 377B | 24 | | PM | PB | 4-2 | 34-12-21 | TB0145Y | | C053 | BJ | | D00351B | J12 | | | ALL |
| 377R | 24 | | PM | PB | 0-0 | 34-12-21 | TB0145Y | | A053 | BJ | | D00351B | H12 | | | ALL |
| 377Y | 24 | | PM | PB | 0-0 | 34-12-21 | TB0145Y | | A054 | BJ | | D00351B | K12 | | | ALL |
| 378B | 24 | | PM | PC | 4-0 | 34-12-21 | D04505P | | 7 | | | TB0145Y | C053 | BJ | | ALL |
| 378R | 24 | | PM | PC | 0-0 | 34-12-21 | D04505P | | 6 | | | TB0145Y | A053 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0140
Page 78
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 378Y | 24 | PM | PC | 0-0 | 34-12-21 | D04505P | | 8 | | | | TB0145Y | A054 | BJ | | ALL |
| 501B | 24 | PW | UA | 4-5 | 31-35-12 | D05763P | | 5 | | | | TB0145Y | C114 | BJ | | 050-099 |
| 501B | 24 | PW | UA | 4-8 | 31-35-12 | D05763P | | 5 | | | | TB0145Y | C114 | BJ | | 150-199, 275-276 |
| 501B | 24 | PW | UA | 4-8 | 31-35-12 | D05763P | | 5 | | | | TB0145Y | C120 | BJ | | 277-299 |
| 501R | 24 | PW | UA | 0-0 | 31-35-12 | D05763P | | 4 | | | | TB0145Y | A114 | BJ | | 050-099, 150-199, 275-276 |
| 501R | 24 | PW | UA | 0-0 | 31-35-12 | D05763P | | 4 | | | | TB0145Y | A120 | BJ | | 277-299 |
| 501Z | | | UA | 0-0 | 31-35-12 | D05763P | | 6 | | | | GDY0003 | S.. | 2 | | ALL |
| 502B | 24 | PW | UB | 4-10 | 31-35-12 | D05763P | | 8 | | | | TB0145Y | C103 | BJ | | 050-099 |
| 502B | 24 | PW | UB | 4-9 | 31-35-12 | D05763P | | 8 | | | | TB0145Y | C103 | BJ | | 150-199, 275-276 |
| 502B | 24 | PW | UB | 4-9 | 31-35-12 | D05763P | | 8 | | | | TB0145Y | C109 | BJ | | 277-299 |
| 502R | 24 | PW | UB | 0-0 | 31-35-12 | D05763P | | 7 | | | | TB0145Y | A103 | BJ | | 050-099, 150-199, 275-276 |
| 502R | 24 | PW | UB | 0-0 | 31-35-12 | D05763P | | 7 | | | | TB0145Y | A109 | BJ | | 277-299 |
| 502Z | | | UB | 0-0 | 31-35-12 | D05763P | | 9 | | | | GDY0001 | S.. | 2 | | ALL |
| 503B | 24 | PW | UC | 4-10 | 31-35-12 | D05763P | | 11 | | | | TB0145Y | C111 | BJ | | 050-099 |
| 503B | 24 | PW | UC | 4-9 | 31-35-12 | D05763P | | 11 | | | | TB0145Y | C111 | BJ | | 150-199, 275-276 |
| 503B | 24 | PW | UC | 4-8 | 31-35-12 | D05763P | | 11 | | | | TB0145Y | C117 | BJ | | 277-299 |
| 503R | 24 | PW | UC | 0-0 | 31-35-12 | D05763P | | 10 | | | | TB0145Y | A111 | BJ | | 050-099, 150-199, 275-276 |
| 503R | 24 | PW | UC | 0-0 | 31-35-12 | D05763P | | 10 | | | | TB0145Y | A117 | BJ | | 277-299 |
| 503Z | | | UC | 0-0 | 31-35-12 | D05763P | | 12 | | | | GDY0002 | S.. | 2 | | ALL |
| 504B | 20 | PB | UD | 4-9 | 34-12-21 | GDY0007 | | A.. | 2 | | | D00351C | 6 | | | ALL |
| 504R | 20 | PB | UD | 0-0 | 34-12-21 | TB0145Z | | 35 | BJ | | | D00351C | 4 | | | ALL |
| 505 | 20 | UA | | 1-6 | 34-12-22 | GDY0012 | | S.. | 2 | | | TB0145Y | REF | | UE | 050-099, 150-199, 275-276 |
| 505B | 24 | PW | UE | 3-9 | 34-12-22 | D00351B | | B02 | | | | TB0145Y | C167 | BJ | | ALL |
| 505R | 24 | PW | UE | 0-0 | 34-12-22 | D00351B | | A02 | | | | TB0145Y | A167 | BJ | | ALL |
| 505Z | | | UE | 0-0 | 34-12-22 | D00351B | | DED | | | | TB0145Y | REF | | UE | 050-099, 150-199, 275-276 |
| 505Z | | | UE | 0-0 | 34-12-22 | D00351B | | DED | | | | GDY0011 | S.. | 2 | | 277-299 |
| 506B | 24 | PW | UF | 4-10 | 31-35-12 | D05763P | | 14 | | | | TB0145Y | C012 | BJ | | 050-099, 150-199, 275-276 |
| 506B | 24 | PW | UF | 4-7 | 31-35-12 | D05763P | | 14 | | | | TB0145Y | C018 | BJ | | 277-299 |
| 506R | 24 | PW | UF | 0-0 | 31-35-12 | D05763P | | 13 | | | | TB0145Y | A012 | BJ | | 050-099, 150-199, 275-276 |
| 506R | 24 | PW | UF | 0-0 | 31-35-12 | D05763P | | 13 | | | | TB0145Y | A018 | BJ | | 277-299 |
| 506Z | | | UF | 0-0 | 31-35-12 | D05763P | | 15 | | | | GDY0002 | S.. | 2 | | ALL |
| 507B | 24 | PW | UG | 4-5 | 31-35-12 | D05763P | | 23 | | | | TB0145Y | C113 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 79

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 507B | 24 | PW | UG | 4-8 | 31-35-12 | D05763P | 23 | | | | TB0145Y | C113 | BJ | | 150-199, 275-276 | |
| 507B | 24 | PW | UG | 4-8 | 31-35-12 | D05763P | 23 | | | | TB0145Y | C119 | BJ | | 277-299 | |
| 507R | 24 | PW | UG | 0-0 | 31-35-12 | D05763P | 22 | | | | TB0145Y | A113 | BJ | | 050-099, 150-199, 275-276 | |
| 507R | 24 | PW | UG | 0-0 | 31-35-12 | D05763P | 22 | | | | TB0145Y | A119 | BJ | | 277-299 | |
| 507Z | | | UG | 0-0 | 31-35-12 | D05763P | 24 | | | | GDY0003 | S.. | 2 | | 050-099, 150-199, 275-276 | |
| 507Z | | | UG | 0-0 | 31-35-12 | D05763P | 24 | | | | GDY0002 | S.. | 2 | | 277-299 | |
| 509B | 20 | PB | UI | 4-9 | 34-12-21 | GDY0007 | A.. | 2 | | | D00351C | 9 | | | ALL | |
| 509R | 20 | PB | UI | 0-0 | 34-12-21 | TB0145Z | 36 | BJ | | | D00351C | 5 | | | ALL | |
| 510B | 20 | PB | UJ | 4-9 | 34-12-21 | GDY0007 | A.. | 2 | | | D00351C | 11 | | | ALL | |
| 510R | 20 | PB | UJ | 0-0 | 34-12-21 | TB0145Z | 36 | BJ | | | D00351C | 10 | | | ALL | |
| 511B | 24 | PW | UK | 4-3 | 34-12-22 | TB0145Z | 52 | BJ | | | D00351B | B08 | | | ALL | |
| 511R | 24 | PW | UK | 0-0 | 34-12-22 | TB0145Z | 51 | BJ | | | D00351B | A08 | | | ALL | |
| 511Z | | | UK | 0-0 | 34-12-22 | GDY0010 | S.. | 2 | | | D00351B | DED | | | 050-099, 150-199, 275-276 | |
| 511Z | | | UK | 0-0 | 34-12-22 | GDY0009 | S.. | 2 | | | D00351B | DED | | | 277-299 | |
| 512 | 20 | UA | | 1-6 | 34-12-62 | D00351B | REF | | UL | | GDX0014 | S.. | 2 | | ALL | |
| 512B | 24 | PW | UL | 3-6 | 34-12-62 | D00351B | B06 | | | | D05715J | 19 | | | ALL | |
| 512R | 24 | PW | UL | 0-0 | 34-12-62 | D00351B | A06 | | | | D05715J | 20 | | | ALL | |
| 512Z | | | UL | 0-0 | 34-12-62 | D00351B | REF | | UL | | D05715J | 21 | | | ALL | |
| 513 | 20 | UA | | 1-6 | 34-12-22 | GDY0011 | S.. | 2 | | | TB0145Z | REF | | UM | 050-099, 150-199, 275-276 | |
| 513B | 24 | PW | UM | 3-10 | 34-12-22 | TB0145Z | 62 | BJ | | | D00351B | B04 | | | ALL | |
| 513R | 24 | PW | UM | 0-0 | 34-12-22 | TB0145Z | 61 | BJ | | | D00351B | A04 | | | ALL | |
| 513Z | | | UM | 0-0 | 34-12-22 | D00351B | DED | | | | TB0145Z | REF | | UM | 050-099, 275-276 | |
| 513Z | | | UM | 0-0 | 34-12-22 | TB0145Z | REF | | UM | | D00351B | DED | | | 150-199 | |
| 513Z | | | UM | 0-0 | 34-12-22 | D00351B | DED | | | | GDY0010 | S.. | 2 | | 277-299 | |
| 514B | 24 | PW | UN | 3-3 | 34-12-22 | TB0145Z | 52 | BJ | | | TB0145Z | 40 | BJ | | ALL | |
| 514R | 24 | PW | UN | 0-0 | 34-12-22 | TB0145Z | 51 | BJ | | | TB0145Z | 39 | BJ | | ALL | |
| 514Z | | | UN | 0-0 | 34-12-22 | GDY0007 | S.. | 2 | | | TB0145Z | DED | | | 050-099, 150-199, 275-276 | |
| 514Z | | | UN | 0-0 | 34-12-22 | GDY0009 | S.. | 2 | | | TB0145Z | DED | | | 277-299 | |
| 515 | 20 | UA | | 1-6 | 34-12-22 | GDY0012 | S.. | 2 | | | TB0145Y | REF | | UO | 050-099, 150-199, 275-276 | |
| 515B | 24 | PW | UO | 3-6 | 34-12-22 | D04821P | 30 | | | | TB0145Y | C167 | BJ | | ALL | |
| 515R | 24 | PW | UO | 0-0 | 34-12-22 | D04821P | 29 | | | | TB0145Y | A167 | BJ | | ALL | |
| 515Z | | | UO | 0-0 | 34-12-22 | D04821P | 31 | | | | TB0145Y | REF | | UO | 050-099, 150-199, 275-276 | |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 80
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | | |
| 515Z | | | | UO | 0-0 | 34-12-22 | D04821P | | 31 | | | | | GDY0011 | S.. | 2 | 277-299 |
| 516 | 20 | | UA | | 1-6 | 31-31-12 | TB0145Y | | REF | | | UP | | GDY0007 | S.. | 2 | 050-099, 152-199, 275-299 |
| 516B | 24 | | PW | UP | 4-3 | 31-31-12 | TB0145Y | | C143 | BJ | | | | D04667P | | 8 | ALL |
| 516R | 24 | | PW | UP | 0-0 | 31-31-12 | TB0145Y | | A143 | BJ | | | | D04667P | | 9 | ALL |
| 516Z | | | | UP | 0-0 | 31-31-12 | TB0145Y | | REF | | | UP | | D04667P | | 36 | 050-099, 152-199, 275-299 |
| 516Z | | | | UP | 0-0 | 31-31-12 | GDY0008 | | S.. | 2 | | | | D04667P | | 36 | 150-151 |
| 522B | 22 | | PB | UV | 4-10 | 34-12-21 | GDY0007 | | A.. | 2 | | | | D04317P | | 5 | ALL |
| 522R | 22 | | PB | UV | 0-0 | 34-12-21 | TB0145Z | | 36 | BJ | | | | D04317P | | 4 | ALL |
| 524B | 22 | | PB | UX | 4-8 | 34-12-21 | D04505P | | 5 | | | | | GDY0007 | A.. | 2 | ALL |
| 524R | 22 | | PB | UX | 0-0 | 34-12-21 | D04505P | | 4 | | | | | TB0145Z | 35 | BJ | ALL |
| 525 | 20 | | UA | | 1-6 | 34-21-21 | GDY0011 | | S.. | 2 | | | | TB0145Z | REF | | UY 050-099, 150-199 |
| 525 | 20 | | UA | | 1-6 | 34-21-21 | GDY0011 | | S.. | 2 | | | | TB0145Y | REF | | UY 275-276 |
| 525B | 24 | | PW | UY | 3-4 | 34-21-21 | D04767P | | 5 | | | | | TB0145Z | 62 | BJ | ALL |
| 525R | 24 | | PW | UY | 0-0 | 34-21-21 | D04767P | | 4 | | | | | TB0145Z | 61 | BJ | ALL |
| 525Z | | | | UY | 0-0 | 34-21-21 | D04767P | | 6 | | | | | TB0145Z | REF | | UY 050-099, 150-199 |
| 525Z | | | | UY | 0-0 | 34-21-21 | D04767P | | 6 | | | | | TB0145Y | REF | | UY 275-276 |
| 525Z | | | | UY | 0-0 | 34-21-21 | D04767P | | 6 | | | | | GDY0010 | S.. | 2 | 277-299 |
| 526B | 24 | | PW | VA | 5-2 | 34-21-21 | D04767P | | 8 | | | | | TB0145Z | 16 | BJ | 050-099, 150-199, 275-276 |
| 526B | 24 | | PW | VA | 4-11 | 34-21-21 | D04767P | | 8 | | | | | TB0145Z | 22 | BJ | 277-299 |
| 526R | 24 | | PW | VA | 0-0 | 34-21-21 | D04767P | | 7 | | | | | TB0145Z | 15 | BJ | 050-099, 150-199, 275-276 |
| 526R | 24 | | PW | VA | 0-0 | 34-21-21 | D04767P | | 7 | | | | | TB0145Z | 21 | BJ | 277-299 |
| 526Z | | | | VA | 0-0 | 34-21-21 | D04767P | | 9 | | | | | GDY0003 | S.. | 2 | ALL |
| 529 | 20 | | UA | | 1-6 | 31-31-14 | TB0145X | | REF | | | VD | | GDY0006 | S.. | 2 | 050-099, 152-199, 275-299 |
| 529B | 24 | | PW | VD | 2-9 | 31-31-14 | TB0145X | | A142 | BJ | | | | D05715J | | 31 | ALL |
| 529R | 24 | | PW | VD | 0-0 | 31-31-14 | TB0145X | | A141 | BJ | | | | D05715J | | 30 | ALL |
| 529Z | | | | VD | 0-0 | 31-31-14 | TB0145X | | REF | | | VD | | D05715J | | 29 | 050-099, 152-199, 275-299 |
| 529Z | | | | VD | 0-0 | 31-31-14 | GDY0008 | | S.. | 2 | | | | D05715J | | 29 | 150-151 |
| 530B | 24 | | PW | VE | 4-10 | 34-13-11 | D04899P | | 24 | | | | | TB0145Z | 52 | BJ | ALL |
| 530R | 24 | | PW | VE | 0-0 | 34-13-11 | D04899P | | 25 | | | | | TB0145Z | 51 | BJ | ALL |
| 530Z | | | | VE | 0-0 | 34-13-11 | D04899P | | 26 | | | | | GDY0010 | S.. | 2 | 050-099, 150-199, 275-276 |
| 530Z | | | | VE | 0-0 | 34-13-11 | D04899P | | 26 | | | | | GDY0009 | S.. | 2 | 277-299 |
| 535B | 24 | | PW | VJ | 2-8 | 21-31-21 | D05715J | | 7 | | | | | TB0145Z | 52 | BJ | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 81

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | From | | | To | | | Effectivity | | | | |
|------------------------|-----------------|----|----|---------------------------------|----------|---------|-------|------|------|--------|-------------|-------|------|------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | | Equip | Term | Type | Splice |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 535R | 24 | PW | VJ | 0-0 | 21-31-21 | D05715J | | 6 | | | TB0145Z | 51 | BJ | | ALL |
| 535Z | | | VJ | 0-0 | 21-31-21 | D05715J | | 5 | | | GDY0010 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 535Z | | | VJ | 0-0 | 21-31-21 | D05715J | | 5 | | | GDY0009 | S.. | 2 | | 277-299 |
| 536B | 24 | PW | VK | 4-10 | 21-31-11 | D04339P | | 17 | | | TB0145Z | 52 | BJ | | ALL |
| 536R | 24 | PW | VK | 0-0 | 21-31-11 | D04339P | | 16 | | | TB0145Z | 51 | BJ | | ALL |
| 536Z | | | VK | 0-0 | 21-31-11 | D04339P | | 18 | | | GDY0010 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 536Z | | | VK | 0-0 | 21-31-11 | D04339P | | 18 | | | GDY0009 | S.. | 2 | | 277-299 |
| 537B | 24 | PW | VL | 5-1 | 31-31-12 | D05439P | | REF | JB | | TB0145Y | C029 | BJ | | ALL |
| 537R | 24 | PW | VL | 0-0 | 31-31-12 | D05439P | | REF | JB | | TB0145Y | A029 | BJ | | ALL |
| 537Z | | | VL | 0-0 | 31-31-12 | D05439P | | REF | JB | | GDY0006 | S.. | 2 | | ALL |
| 538B | 24 | PW | VM | 4-6 | 31-31-12 | D04767P | | 27 | | | TB0145X | D145 | BJ | | 050-099, 150-152, 155-199, 275-299 |
| 538B | 24 | PW | VM | 4-6 | 31-31-12 | D04767P | | 43 | | | TB0145X | D145 | BJ | | 153-154 |
| 538R | 24 | PW | VM | 0-0 | 31-31-12 | D04767P | | 20 | | | TB0145X | C145 | BJ | | ALL |
| 538Z | | | VM | 0-0 | 31-31-12 | D04767P | | 21 | | | GDY0009 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 538Z | | | VM | 0-0 | 31-31-12 | D04767P | | 21 | | | GDY0008 | S.. | 2 | | 277-299 |
| 539 | 20 | UA | | 1-6 | 34-61-25 | D00353B | | | | VN | GDY0012 | S.. | 2 | | ALL |
| 539B | 24 | PW | VN | 3-5 | 34-61-25 | D04811P | | 33 | | | D00353B | B09 | ** | | 050-099, 150-166 |
| 539B | 24 | PW | VN | 3-5 | 34-61-25 | D04811P | | 33 | | | D00353B | B09 | ** | | 167-199, 275-299 |
| 539R | 24 | PW | VN | 0-0 | 34-61-25 | D04811P | | 32 | | | D00353B | A09 | ** | | 050-099, 150-166 |
| 539R | 24 | PW | VN | 0-0 | 34-61-25 | D04811P | | 32 | | | D00353B | A09 | ** | | 167-199, 275-299 |
| 539Z | | | VN | 0-0 | 34-61-25 | D04811P | | 34 | | | D00353B | | | VN | ALL |
| 540 | 20 | UA | | 1-6 | 34-61-25 | GDY0011 | | S.. | 2 | | TB0145Z | REF | | VO | 050-099, 150-199, 275-276 |
| 540B | 24 | PW | VO | 3-10 | 34-61-25 | D05065P | | 23 | | | TB0145Z | 58 | BJ | | 050-099, 150-199, 275-276 |
| 540B | 24 | PW | VO | 3-3 | 34-61-25 | D05065P | | 23 | | | TB0145Z | 80 | BJ | | 277-299 |
| 540R | 24 | PW | VO | 0-0 | 34-61-25 | D05065P | | 22 | | | TB0145Z | 57 | BJ | | 050-099, 150-199, 275-276 |
| 540R | 24 | PW | VO | 0-0 | 34-61-25 | D05065P | | 22 | | | TB0145Z | 79 | BJ | | 277-299 |
| 540Z | | | VO | 0-0 | 34-61-25 | D05065P | | 24 | | | TB0145Z | REF | | VO | 050-099, 150-199, 275-276 |
| 540Z | | | VO | 0-0 | 34-61-25 | D05065P | | 24 | | | GDY0012 | S.. | 2 | | 277-299 |
| 541 | 20 | UA | | 1-6 | 34-61-25 | D00353B | | | | VP | GDY0012 | S.. | 2 | | ALL |
| 541B | 24 | PW | VP | 3-5 | 34-61-25 | D04811P | | 36 | | | D00353B | H03 | ** | | 050-099, 150-166 |
| 541B | 24 | PW | VP | 3-5 | 34-61-25 | D04811P | | 36 | | | D00353B | REF | ** | | 167-199 |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 82
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 541B | 24 | PW | VP | | 3-5 | 34-61-25 | D04811P | | 36 | | | D00353B | H03 | | | 275-299 |
| 541R | 24 | PW | VP | | 0-0 | 34-61-25 | D04811P | | 35 | | | D00353B | G03 | ** | | 050-099, 150-166 |
| 541R | 24 | PW | VP | | 0-0 | 34-61-25 | D04811P | | 35 | | | D00353B | REF | ** | | 167-199 |
| 541R | 24 | PW | VP | | 0-0 | 34-61-25 | D04811P | | 35 | | | D00353B | G03 | | | 275-299 |
| 541Z | | | VP | | 0-0 | 34-61-25 | D04811P | | 37 | | | D00353B | | | VP | ALL |
| 542B | 24 | PW | VQ | | 4-1 | 22-32-11 | D04767P | | 23 | | | TB0145Z | 40 | BJ | | ALL |
| 542R | 24 | PW | VQ | | 0-0 | 22-32-11 | D04767P | | 22 | | | TB0145Z | 39 | BJ | | ALL |
| 542Z | | | VQ | | 0-0 | 22-32-11 | D04767P | | 24 | | | GDY0007 | S.. | 2 | | ALL |
| 543B | 24 | PW | VR | | 4-6 | 31-41-33 | D05065P | | 17 | | | D05713P | 48 | | | ALL |
| 543R | 24 | PW | VR | | 0-0 | 31-41-33 | D05065P | | 16 | | | D05713P | 47 | | | ALL |
| 543Z | | | VR | | 0-0 | 31-41-33 | D05065P | | 18 | | | D05713P | 49 | | | ALL |
| 544 | 20 | UA | | | 1-6 | 31-41-33 | GDX0006 | | S.. | 2 | | TB0145Z | REF | | VS | 050-099, 152-199, 275-276 |
| 544B | 24 | PW | VS | | 4-3 | 31-41-33 | D05065P | | 20 | | | TB0145Z | 40 | BJ | | ALL |
| 544R | 24 | PW | VS | | 0-0 | 31-41-33 | D05065P | | 19 | | | TB0145Z | 39 | BJ | | ALL |
| 544Z | | | VS | | 0-0 | 31-41-33 | D05065P | | 21 | | | TB0145Z | REF | | VS | 050-099, 152-199, 275-276 |
| 544Z | | | VS | | 0-0 | 31-41-33 | D05065P | | 21 | | | GDY0008 | S.. | 2 | | 150-151 |
| 544Z | | | VS | | 0-0 | 31-41-33 | D05065P | | 21 | | | GDY0007 | S.. | 2 | | 277-299 |
| 545B | 24 | PW | VT | | 3-6 | 31-35-13 | TB0145Z | | 56 | BJ | | D05713P | 16 | | | 050-099, 150-199, 275-276 |
| 545B | 24 | PW | VT | | 4-1 | 31-35-13 | TB0145Z | | 78 | BJ | | D05713P | 16 | | | 277-299 |
| 545R | 24 | PW | VT | | 0-0 | 31-35-13 | TB0145Z | | 55 | BJ | | D05713P | 15 | | | 050-099, 150-199, 275-276 |
| 545R | 24 | PW | VT | | 0-0 | 31-35-13 | TB0145Z | | 77 | BJ | | D05713P | 15 | | | 277-299 |
| 545Z | | | VT | | 0-0 | 31-35-13 | GDY0010 | | S.. | 2 | | D05713P | 17 | | | 050-099, 150-199, 275-276 |
| 545Z | | | VT | | 0-0 | 31-35-13 | GDY0012 | | S.. | 2 | | D05713P | 17 | | | 277-299 |
| 551B | 24 | PW | WA | | 3-7 | 31-35-12 | D05763P | | 26 | | | TB0145Y | C034 | BJ | | ALL |
| 551R | 24 | PW | WA | | 0-0 | 31-35-12 | D05763P | | 25 | | | TB0145Y | A034 | BJ | | ALL |
| 551Z | | | WA | | 0-0 | 31-35-12 | D05763P | | 27 | | | GDY0006 | S.. | 2 | | ALL |
| 552B | 24 | PW | WB | | 4-10 | 31-35-12 | D05763P | | 29 | | | TB0145Y | C101 | BJ | | 050-099 |
| 552B | 24 | PW | WB | | 4-9 | 31-35-12 | D05763P | | 29 | | | TB0145Y | C101 | BJ | | 150-199, 275-276 |
| 552B | 24 | PW | WB | | 4-9 | 31-35-12 | D05763P | | 29 | | | TB0145Y | C107 | BJ | | 277-299 |
| 552R | 24 | PW | WB | | 0-0 | 31-35-12 | D05763P | | 28 | | | TB0145Y | A101 | BJ | | 050-099, 150-199, 275-276 |
| 552R | 24 | PW | WB | | 0-0 | 31-35-12 | D05763P | | 28 | | | TB0145Y | A107 | BJ | | 277-299 |
| 552Z | | | WB | | 0-0 | 31-35-12 | D05763P | | 30 | | | GDY0001 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 83

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 553B | 24 | PW | WC | 4-10 | 31-35-12 | D05763P | | 32 | | TB0145Y | C011 | BJ | | 050-099, 150-199, 275-276 | |
| 553B | 24 | PW | WC | 4-7 | 31-35-12 | D05763P | | 32 | | TB0145Y | C017 | BJ | | 277-299 | |
| 553R | 24 | PW | WC | 0-0 | 31-35-12 | D05763P | | 31 | | TB0145Y | A011 | BJ | | 050-099, 150-199, 275-276 | |
| 553R | 24 | PW | WC | 0-0 | 31-35-12 | D05763P | | 31 | | TB0145Y | A017 | BJ | | 277-299 | |
| 553Z | | | WC | 0-0 | 31-35-12 | D05763P | | 33 | | GDY0002 | S.. | 2 | | ALL | |
| 554 | 20 | UA | | 1-6 | 31-35-12 | GDY0008 | | S.. | 2 | TB0145Y | REF | | WD | 050-099 | |
| 554 | 20 | UA | | 1-6 | 31-35-12 | GDY0013 | | S.. | 2 | TB0145Y | REF | | WD | 150-151 | |
| 554 | 20 | UA | | 1-6 | 31-35-12 | GDX0006 | | S.. | 2 | TB0145Y | REF | | WD | 152-156, 162-166 | |
| 554 | 20 | UA | | 1-6 | 31-35-12 | GDX0011 | | S.. | 2 | TB0145Z | REF | | WD | 157, 167-199, 275-276 | |
| 554 | 20 | UA | | 1-6 | 31-35-12 | GDX0003 | | S.. | 2 | TB0145Z | REF | | WD | 277-278 | |
| 554 | 20 | UA | | 1-6 | 31-35-12 | GDX0003 | | S.. | 2 | TB0145Y | REF | | WD | 280-299 | |
| 554B | 24 | PW | WD | 3-7 | 31-35-12 | D05763P | | 35 | | TB0145Y | C033 | BJ | | 050-099, 150-156, 162-166 | |
| 554B | 24 | PW | WD | 2-6 | 31-35-12 | D05763P | | 35 | | TB0145Z | 182 | BJ | | 157, 167-199 | |
| 554B | 24 | PW | WD | 2-6 | 31-35-12 | D05763P | | 35 | | TB0145Z | 184 | BJ | | 275-276 | |
| 554B | 24 | PW | WD | 4-4 | 31-35-12 | D05763P | | 35 | | TB0145Z | 126 | BJ | | 277-299 | |
| 554R | 24 | PW | WD | 0-0 | 31-35-12 | D05763P | | 34 | | TB0145Y | A033 | BJ | | 050-099, 150-156, 162-166 | |
| 554R | 24 | PW | WD | 0-0 | 31-35-12 | D05763P | | 34 | | TB0145Z | 181 | BJ | | 157, 167-199 | |
| 554R | 24 | PW | WD | 0-0 | 31-35-12 | D05763P | | 34 | | TB0145Z | 183 | BJ | | 275-276 | |
| 554R | 24 | PW | WD | 0-0 | 31-35-12 | D05763P | | 34 | | TB0145Z | 125 | BJ | | 277-299 | |
| 554Z | | | WD | 0-0 | 31-35-12 | D05763P | | 36 | | TB0145Y | REF | | WD | 050-099, 150-156, 162-166, 280-299 | |
| 554Z | | | WD | 0-0 | 31-35-12 | D05763P | | 36 | | TB0145Z | REF | | WD | 157, 167-199, 275-278 | |
| 555B | 24 | PW | WE | 4-10 | 31-35-12 | D05763P | | 38 | | TB0145Y | C109 | BJ | | 050-099 | |
| 555B | 24 | PW | WE | 4-9 | 31-35-12 | D05763P | | 38 | | TB0145Y | C109 | BJ | | 150-199, 275-276 | |
| 555B | 24 | PW | WE | 4-8 | 31-35-12 | D05763P | | 38 | | TB0145Y | C115 | BJ | | 277-299 | |
| 555R | 24 | PW | WE | 0-0 | 31-35-12 | D05763P | | 37 | | TB0145Y | A109 | BJ | | 050-099, 150-199, 275-276 | |
| 555R | 24 | PW | WE | 0-0 | 31-35-12 | D05763P | | 37 | | TB0145Y | A115 | BJ | | 277-299 | |
| 555Z | | | WE | 0-0 | 31-35-12 | D05763P | | 39 | | GDY0002 | S.. | 2 | | ALL | |
| 557B | 24 | PW | WG | 5-1 | 34-61-26 | D02281 | | B3 | | TB0145Z | 16 | BJ | | 050-099, 150-199, 275-276 | |
| 557B | 24 | PW | WG | 4-10 | 34-61-26 | D02281 | | B3 | | TB0145Z | 22 | BJ | | 277-299 | |
| 557R | 24 | PW | WG | 0-0 | 34-61-26 | D02281 | | A3 | | TB0145Z | 15 | BJ | | 050-099, 150-199, 275-276 | |
| 557R | 24 | PW | WG | 0-0 | 34-61-26 | D02281 | | A3 | | TB0145Z | 21 | BJ | | 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 84

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|-----|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | | | |
| 557Z | | | | WG | 0-0 | 34-61-26 | D02281 | | DED | | | | | GDY0003 | S.. | 2 | | ALL |
| 558 | 20 | | UA | | 1-6 | 34-61-26 | D02281 | | REF | | | WH | | GDY0003 | S.. | 2 | | ALL |
| 558B | 24 | | PW | WH | 4-3 | 34-61-26 | D02281 | | B1 | | | | | D05713P | 42 | | | ALL |
| 558R | 24 | | PW | WH | 0-0 | 34-61-26 | D02281 | | A1 | | | | | D05713P | 41 | | | ALL |
| 558Z | | | | WH | 0-0 | 34-61-26 | D02281 | | REF | | | WH | | D05713P | 43 | | | ALL |
| 559B | 24 | | PW | WI | 4-4 | 34-61-26 | D04433P | | 14 | | | | | TB0145Z | 56 | BJ | | 050-099, 150-199, 275-276 |
| 559B | 24 | | PW | WI | 3-10 | 34-61-26 | D04433P | | 14 | | | | | TB0145Z | 78 | BJ | | 277-299 |
| 559R | 24 | | PW | WI | 0-0 | 34-61-26 | D04433P | | 13 | | | | | TB0145Z | 55 | BJ | | 050-099, 150-199, 275-276 |
| 559R | 24 | | PW | WI | 0-0 | 34-61-26 | D04433P | | 13 | | | | | TB0145Z | 77 | BJ | | 277-299 |
| 559Z | | | | WI | 0-0 | 34-61-26 | D04433P | | 15 | | | | | GDY0010 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 559Z | | | | WI | 0-0 | 34-61-26 | D04433P | | 15 | | | | | GDY0012 | S.. | 2 | | 277-299 |
| 560 | 20 | | UA | | 1-6 | 34-61-26 | D02277 | | REF | | | WG | | GDY0012 | S.. | 2 | | ALL |
| 560B | 24 | | PW | WJ | 2-11 | 34-61-26 | D02277 | | B1 | | | | | D04433P | 17 | | | ALL |
| 560R | 24 | | PW | WJ | 0-0 | 34-61-26 | D02277 | | A1 | | | | | D04433P | 16 | | | ALL |
| 560Z | | | | WJ | 0-0 | 34-61-26 | D02277 | | REF | | | WG | | D04433P | 18 | | | ALL |
| 561 | 20 | | UA | | 1-6 | 34-61-26 | D02277 | | REF | | | WK | | GDY0013 | S.. | 2 | | ALL |
| 561B | 24 | | PW | WK | 4-3 | 34-61-26 | D02277 | | B3 | | | | | D05713P | 30 | | | ALL |
| 561R | 24 | | PW | WK | 0-0 | 34-61-26 | D02277 | | A3 | | | | | D05713P | 29 | | | ALL |
| 561Z | | | | WK | 0-0 | 34-61-26 | D02277 | | REF | | | WK | | D05713P | 31 | | | ALL |
| 566 | 24 | | PK | | 2-9 | 31-31-14 | TB0145X | | D141 | BJ | | | | D05715J | 28 | | | ALL |
| 567 | 24 | | PK | | 4-11 | 31-51-21 | TB0145X | | A038 | BJ | | | | D04819P | 22 | | | ALL |
| 568 | 20 | | UA | | 1-6 | 31-41-35 | GDY0012 | | S.. | 2 | | | | TB0145X | | REF | WR | 050-099, 150-199, 275-276 |
| 568B | 24 | | PW | WR | 4-2 | 31-41-35 | D04819P | | 45 | | | | | TB0145X | D068 | BJ | | ALL |
| 568R | 24 | | PW | WR | 0-0 | 31-41-35 | D04819P | | 42 | | | | | TB0145X | C068 | BJ | | ALL |
| 568Z | | | | WR | 0-0 | 31-41-35 | D04819P | | 48 | | | | | TB0145X | REF | | WR | 050-099, 150-199, 275-276 |
| 568Z | | | | WR | 0-0 | 31-41-35 | D04819P | | 48 | | | | | GDY0011 | S.. | 2 | | 277-299 |
| 570 | 20 | | UA | | 1-6 | 28-41-11 | GDY0012 | | S.. | 2 | | | | TB0145X | REF | | WT | 050-099, 150-199, 275-276 |
| 570B | 24 | | PW | WT | 4-2 | 28-41-11 | D04819P | | 53 | | | | | TB0145X | B068 | BJ | | ALL |
| 570R | 24 | | PW | WT | 0-0 | 28-41-11 | D04819P | | 51 | | | | | TB0145X | A068 | BJ | | ALL |
| 570Z | | | | WT | 0-0 | 28-41-11 | D04819P | | 55 | | | | | TB0145X | REF | | WT | 050-099, 150-199, 275-276 |
| 570Z | | | | WT | 0-0 | 28-41-11 | D04819P | | 55 | | | | | GDY0011 | S.. | 2 | | 277-299 |
| 571 | 20 | | UA | | 1-6 | 27-11-12 | GDY0011 | | S.. | 2 | | | | TB0145Y | REF | | WU | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 85

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 571 | 20 | | UA | | 1-6 | 27-11-12 | GDY0011 | S.. | 2 | | TB0145Z | REF | | WU | 150-199, 275-276 |
| 571B | 24 | | PW | WU | 3-6 | 27-11-12 | D05407P | | 8 | | TB0145Z | 62 | BJ | | ALL |
| 571R | 24 | | PW | WU | 0-0 | 27-11-12 | D05407P | | 7 | | TB0145Z | 61 | BJ | | ALL |
| 571Z | | | | WU | 0-0 | 27-11-12 | D05407P | | 9 | | TB0145Y | REF | | WU | 050-099 |
| 571Z | | | | WU | 0-0 | 27-11-12 | D05407P | | 9 | | TB0145Z | REF | | WU | 150-199, 275-276 |
| 571Z | | | | WU | 0-0 | 27-11-12 | D05407P | | 9 | | GDY0010 | S.. | 2 | | 277-299 |
| 572 | 20 | | UA | | 1-6 | 34-13-21 | GDY0011 | S.. | 2 | | TB0145Z | REF | | WV | 050-099, 150-199, 275-276 |
| 572B | 24 | | PW | WV | 3-9 | 34-13-21 | D04505P | | 10 | | TB0145Z | 62 | BJ | | ALL |
| 572R | 24 | | PW | WV | 0-0 | 34-13-21 | D04505P | | 9 | | TB0145Z | 61 | BJ | | ALL |
| 572Z | | | | WV | 0-0 | 34-13-21 | D04505P | | 11 | | TB0145Z | REF | | WV | 050-099, 150-199, 275-276 |
| 572Z | | | | WV | 0-0 | 34-13-21 | D04505P | | 11 | | GDY0010 | S.. | 2 | | 277-299 |
| 573 | 20 | | UA | | 1-6 | 34-21-31 | TB0145Z | REF | | WW | GDX0006 | S.. | 2 | | 050-099, 152-199, 275-276 |
| 573B | 24 | | PW | WW | 4-1 | 34-21-31 | D04767P | | 51 | | TB0145Z | 40 | BJ | | ALL |
| 573R | 24 | | PW | WW | 0-0 | 34-21-31 | D04767P | | 50 | | TB0145Z | 39 | BJ | | ALL |
| 573Z | | | | WW | 0-0 | 34-21-31 | D04767P | | 52 | | TB0145Z | REF | | WW | 050-099, 152-199, 275-276 |
| 573Z | | | | WW | 0-0 | 34-21-31 | D04767P | | 52 | | GDY0008 | S.. | 2 | | 150-151 |
| 573Z | | | | WW | 0-0 | 34-21-31 | D04767P | | 52 | | GDY0007 | S.. | 2 | | 277-299 |
| 574B | 24 | | PW | WX | 4-3 | 23-22-11 | D04811P | | 26 | | TB0145Y | C144 | BJ | | ALL |
| 574R | 24 | | PW | WX | 0-0 | 23-22-11 | D04811P | | 25 | | TB0145Y | A144 | BJ | | ALL |
| 574Z | | | | WX | 0-0 | 23-22-11 | D04811P | | 27 | | GDY0008 | S.. | 2 | | ALL |
| 576 | 20 | | UA | | 1-6 | 34-61-26 | D02283 | REF | | XA | GDX0013 | S.. | 2 | | ALL |
| 576B | 24 | | PW | XA | 2-0 | 34-61-26 | D02283 | | B3 | | D02281 | B2 | | | ALL |
| 576R | 24 | | PW | XA | 0-0 | 34-61-26 | D02283 | | A3 | | D02281 | A2 | | | ALL |
| 576Z | | | | XA | 0-0 | 34-61-26 | D02283 | REF | | XA | D02281 | DED | | | ALL |
| 577 | 20 | | UA | | 1-6 | 34-61-26 | D02283 | REF | | XB | GDX0013 | S.. | 2 | | ALL |
| 577B | 24 | | PW | XB | 4-3 | 34-61-26 | D02283 | | B1 | | D05713P | 52 | | | ALL |
| 577R | 24 | | PW | XB | 0-0 | 34-61-26 | D02283 | | A1 | | D05713P | 51 | | | ALL |
| 577Z | | | | XB | 0-0 | 34-61-26 | D02283 | REF | | XB | D05713P | 53 | | | ALL |
| 578B | 24 | | PW | XC | 4-1 | 34-12-62 | D04819P | | 8 | | D03693P | 16 | | | ALL |
| 578R | 24 | | PW | XC | 0-0 | 34-12-62 | D04819P | | 7 | | D03693P | 17 | | | ALL |
| 578Z | | | | XC | 0-0 | 34-12-62 | D04819P | | 6 | | D03693P | 18 | | | ALL |
| 585B | 22 | | PR | XJ | 3-5 | 34-12-21 | D00351B | | J08 | | D04899P | 18 | | | ALL |
| 585R | 22 | | PR | XJ | 0-0 | 34-12-21 | D00351B | | H08 | | D04899P | 17 | | | ALL |
| 585Z | | | | XJ | 0-0 | 34-12-21 | D00351B | | K08 | | D04899P | 19 | | | ALL |
| 586B | 24 | | PW | XK | 3-6 | 34-12-22 | TB0145Z | | 52 | BJ | TB0145Y | C029 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0140
Page 86
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 586R | 24 | PW | XK | 0-0 | 34-12-22 | TB0145Z | 51 | BJ | | TB0145Y | A029 | BJ | | ALL | | |
| 586Z | | | XK | 0-0 | 34-12-22 | GDY0006 | S.. | 2 | | TB0145Y | DED | | | 050-099, 150-199, 275-276 | | |
| 586Z | | | XK | 0-0 | 34-12-22 | GDY0009 | S.. | 2 | | TB0145Y | DED | | | 277-299 | | |
| 587 | 20 | UA | | 1-6 | 34-61-26 | GDY0012 | S.. | 2 | | TB0145Y | REF | | XL | 050-099, 150-199, 275-276 | | |
| 587B | 24 | PW | XL | 3-4 | 34-61-26 | D02283 | | B2 | | TB0145Y | C063 | BJ | | ALL | | |
| 587R | 24 | PW | XL | 0-0 | 34-61-26 | D02283 | | A2 | | TB0145Y | A063 | BJ | | ALL | | |
| 587Z | | | XL | 0-0 | 34-61-26 | D02283 | DED | | | TB0145Y | REF | | XL | 050-099, 150-199, 275-276 | | |
| 587Z | | | XL | 0-0 | 34-61-26 | D02283 | DED | | | GDY0010 | S.. | 2 | | 277-299 | | |
| 588 | 20 | UA | | 1-6 | 34-61-26 | GDY0012 | S.. | 2 | | TB0145Y | REF | | XM | 050-099, 150-199, 275-276 | | |
| 588B | 24 | PW | XM | 3-7 | 34-61-26 | D04821P | | 15 | | TB0145Y | C063 | BJ | | ALL | | |
| 588R | 24 | PW | XM | 0-0 | 34-61-26 | D04821P | | 14 | | TB0145Y | A063 | BJ | | ALL | | |
| 588Z | | | XM | 0-0 | 34-61-26 | D04821P | | 16 | | TB0145Y | REF | | XM | 050-099, 150-199, 275-276 | | |
| 588Z | | | XM | 0-0 | 34-61-26 | D04821P | | 16 | | GDY0010 | S.. | 2 | | 277-299 | | |
| 592 | 20 | UA | | 1-6 | 34-61-26 | D02277 | REF | | XQ | GDX0013 | S.. | 2 | | ALL | | |
| 592B | 24 | PW | XQ | 3-1 | 34-61-26 | D02277 | | B2 | | D04821P | 12 | | | ALL | | |
| 592R | 24 | PW | XQ | 0-0 | 34-61-26 | D02277 | | A2 | | D04821P | 11 | | | ALL | | |
| 592Z | | | XQ | 0-0 | 34-61-26 | D02277 | REF | | XQ | D04821P | 13 | | | ALL | | |
| 594 | 20 | UA | | 1-6 | 34-61-26 | D00353B | REF | | XS | GDX0012 | S.. | 2 | | ALL | | |
| 594B | 24 | PW | XS | 3-9 | 34-61-26 | D04433P | | 23 | | D00353B | H02 | | | ALL | | |
| 594R | 24 | PW | XS | 0-0 | 34-61-26 | D04433P | | 22 | | D00353B | G02 | | | ALL | | |
| 594Z | | | XS | 0-0 | 34-61-26 | D04433P | | 24 | | D00353B | REF | | XS | ALL | | |
| 595 | 20 | UA | | 1-6 | 34-61-15 | D00353A | REF | | XT | GDX0012 | S.. | 2 | | ALL | | |
| 595B | 24 | PW | XT | 2-9 | 34-61-15 | D05763P | | 44 | | D00353A | E09 | | | ALL | | |
| 595R | 24 | PW | XT | 0-0 | 34-61-15 | D05763P | | 43 | | D00353A | D09 | | | ALL | | |
| 595Z | | | XT | 0-0 | 34-61-15 | D05763P | | 45 | | D00353A | REF | | XT | ALL | | |
| 596B | 24 | PW | XU | 3-9 | 34-61-15 | D00353A | H11 | | | TB0145X | D047 | BJ | | 050-099, 150-199, 275-276 | | |
| 596B | 24 | PW | XU | 2-11 | 34-61-15 | D00353A | H11 | | | TB0145X | D083 | BJ | | 277-299 | | |
| 596R | 24 | PW | XU | 0-0 | 34-61-15 | D00353A | G11 | | | TB0145X | C047 | BJ | | 050-099, 150-199, 275-276 | | |
| 596R | 24 | PW | XU | 0-0 | 34-61-15 | D00353A | G11 | | | TB0145X | C083 | BJ | | 277-299 | | |
| 596Z | | | XU | 0-0 | 34-61-15 | D00353A | DED | | | GDY0008 | S.. | 2 | | 050-099, 150-199, 275-276 | | |
| 596Z | | | XU | 0-0 | 34-61-15 | D00353A | DED | | | GDY0012 | S.. | 2 | | 277-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 87

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 597B | 24 | PW | XY | | 3-2 | 23-25-13 | D06157P | | 2 | | D04433P | | 11 | | 156-157, 166-199, 277-299 |
| 597R | 24 | PW | XY | | 0-0 | 23-25-13 | D06157P | | 1 | | D04433P | | 9 | | 156-157, 166-199, 277-299 |
| 597Z | | | XY | | 0-0 | 23-25-13 | D06157P | | 3 | | D04433P | | 12 | | 156-157, 166-199, 277-299 |
| 598 | 20 | UA | | | 1-6 | 23-25-13 | TB0145Z | REF | | XW | GDY0007 | S.. | 2 | | 150, 153-199 |
| 598B | 22 | PR | XW | | 4-7 | 23-25-13 | D06157P | | 6 | | TB0145Z | 46 | BJ | | 150, 153-155, 162-165 |
| 598B | 24 | PW | XW | | 4-7 | 23-25-13 | D06157P | | 6 | | TB0145Z | 46 | BJ | | 156-157, 166-199, 277-299 |
| 598R | 22 | PR | XW | | 0-0 | 23-25-13 | D06157P | | 5 | | TB0145Z | 45 | BJ | | 150, 153-155, 162-165 |
| 598R | 24 | PW | XW | | 0-0 | 23-25-13 | D06157P | | 5 | | TB0145Z | 45 | BJ | | 156-157, 166-199, 277-299 |
| 598Z | | | XW | | 0-0 | 23-25-13 | D06157P | | 4 | | TB0145Z | REF | | XW | 150, 153-199 |
| 598Z | | | XW | | 0-0 | 23-25-13 | D06157P | | 4 | | GDY0008 | S.. | 2 | | 277-299 |
| 599B | 24 | PW | XX | | 3-7 | 23-25-13 | D06157P | | 15 | | D04767P | 39 | | | 156-157, 166-199, 277-299 |
| 599R | 24 | PW | XX | | 0-0 | 23-25-13 | D06157P | | 14 | | D04767P | 38 | | | 156-157, 166-199, 277-299 |
| 599Z | | | XX | | 0-0 | 23-25-13 | D06157P | | 13 | | D04767P | 40 | | | 156-157, 166-199, 277-299 |
| 601 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | A01 | | | D01425 | | 1 | | 050-099 |
| 601 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | A01 | | | D01425 | CAP | Y | | 150-199, 275-299 |
| 602 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | B01 | | | D01425 | | 2 | | 050-099, 150, 152-199, 275-299 |
| 602 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | B01 | | | D01425 | CAP | Y | | 151 |
| 603 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | C01 | | | D01425 | | 3 | | 050-099 |
| 603 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | C01 | | | D01425 | CAP | Y | | 150-199, 275-299 |
| 604 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | D01 | | | D01425 | CAP | Y | | ALL |
| 605 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | E01 | | | D01425 | CAP | Y | | 050-099, 150-199 |
| 605 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | E01 | | | D01425 | | 5 | | 275-299 |
| 606 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | F01 | | | D01425 | | 6 | | 050-099, 150-199 |
| 606 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | F01 | | | D01425 | CAP | Y | | 275-299 |
| 607 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | G01 | | | D01425 | CAP | Y | | 050-099, 152, 155, 164, 166, 275-299 |
| 607 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | G01 | | | D01425 | | 7 | | 150-151, 153-154, 156-163, 165, 167-199 |
| 608 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | H01 | | | D01425 | CAP | Y | | 050-099, 275-299 |
| 608 | 24 | PK | | | 2-9 | 34-53-22 | D00359B | H01 | | | D01425 | | 8 | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 88
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|--------|------|------|---|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 609 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | J01 | | | D01425 | CAP | Y | 050-099, 151, 275-299 | | |
| 609 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | J01 | | | D01425 | 9 | | 150, 152-199 | | |
| 610 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | K01 | | | D01425 | 10 | | 050-099, 151, 275-299 | | |
| 610 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | K01 | | | D01425 | CAP | Y | 150, 152-199 | | |
| 611 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | A02 | | | D01425 | CAP | Y | 050-099, 150-151, 153-154, 156-163, 165, 167-199, 275-299 | | |
| 611 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | A02 | | | D01425 | 11 | | 152, 155, 164, 166 | | |
| 612 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | B02 | | | D01425 | CAP | Y | ALL | | |
| 613 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | C02 | | | D01425 | CAP | Y | 050-099, 150-151, 153-154, 156-163, 165, 167-199, 275-299 | | |
| 613 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | C02 | | | D01425 | 13 | | 152, 155, 164, 166 | | |
| 614 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | D02 | | | D01425 | 14 | | 050-099, 152, 155, 164, 166 | | |
| 614 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | D02 | | | D01425 | CAP | Y | 150-151, 153-154, 156-163, 165, 167-199, 275-299 | | |
| 615 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | E02 | | | D01425 | 15 | | 050-099, 165 | | |
| 615 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | E02 | | | D01425 | CAP | Y | 150-164, 166-199, 275-299 | | |
| 616 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | F02 | | | D01425 | CAP | Y | 050-099, 150-164, 166-199, 275-299 | | |
| 616 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | F02 | | | D01425 | 16 | | 165 | | |
| 617 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | G02 | | | D01425 | CAP | Y | 050-099, 150-151, 153-154, 156-163, 165, 275-299 | | |
| 617 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | G02 | | | D01425 | 17 | | 152, 155, 164, 166-199 | | |
| 618 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | H02 | | | D01425 | 18 | | 050-099, 165, 277-299 | | |
| 618 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | H02 | | | D01425 | CAP | Y | 150-164, 166-199, 275-276 | | |
| 619 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | J02 | | | D01425 | CAP | Y | 050-099, 151-152, 155, 162-199, 275-299 | | |
| 619 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | J02 | | | D01425 | 19 | | 150, 153-154, 156-157 | | |
| 620 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | K02 | | | D01425 | 20 | | 050-099, 154, 156-157, 165 | | |
| 620 | 24 | | PK | 2-9 | 34-53-22 | D00359B | | K02 | | | D01425 | CAP | Y | 150-153, 155, 162-164, 166-199, 275-299 | | |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 89
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|---|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 621 | 24 | | PK | | 2-9 | 34-53-22 | D00359B | A03 | | | D01425 | 21 | | | | 050-099, 150, 152-153, 155, 162-199, 276, 278 |
| 621 | 24 | | PK | | 2-9 | 34-53-22 | D00359B | A03 | | | D01425 | CAP | Y | | | 151, 154, 156-157, 275, 277, 280-299 |
| 622 | 24 | | PK | | 2-9 | 34-53-22 | D00359B | B03 | | | D01425 | CAP | Y | | | 050-099, 152-154, 156-157, 163, 167-199, 275-276, 278 |
| 622 | 24 | | PK | | 2-9 | 34-53-22 | D00359B | B03 | | | D01425 | 22 | | | | 150-151, 155, 162, 164-166, 277, 280-299 |
| 623 | 24 | | PK | | 2-9 | 34-53-22 | D00359B | C03 | | | D01425 | CAP | Y | | | 050, 152, 154-156, 162-163, 165-199, 275-278 |
| 623 | 24 | | PK | | 2-9 | 34-53-22 | D00359B | C03 | | | D01425 | 23 | | | | 051-099, 150-151, 153, 157, 164, 280-299 |
| 624 | 24 | | PK | | 2-9 | 34-53-22 | D00359B | D03 | | | D01425 | 24 | | | | 050, 150, 153, 156, 162, 165-166, 276-277, 280-299 |
| 624 | 24 | | PK | | 2-9 | 34-53-22 | D00359B | D03 | | | D01425 | CAP | Y | | | 051-099, 151-152, 154-155, 157, 163-164, 167-199, 275, 278 |
| 625 | 24 | | PK | | 2-9 | 34-53-22 | D00359B | E03 | | | D01425 | 25 | | | | ALL |
| 630 | 20 | | PQ | ZE | 4-3 | 27-32-31 | D04667P | 48 | | | D04819P | 44 | | | | ALL |
| 630Z | | | | ZE | 0-0 | 27-32-31 | D04667P | DED | | | D04819P | DED | | | | ALL |
| 631 | 24 | | PK | | 6-3 | 31-31-21 | D04819P | 49 | | | TB0145R | A025 | 2 | | | 050-099, 150-199, 275-276 |
| 631 | 24 | | PK | | 6-8 | 31-31-21 | D04819P | 49 | | | TB0145R | A102 | 2 | | | 277-299 |
| 632 | 24 | | PK | | 6-9 | 31-31-21 | D04819P | 50 | | | TB0145X | B002 | BJ | | | 050-099, 150-199, 275-276 |
| 632 | 24 | | PK | | 6-9 | 31-31-21 | D04819P | 50 | | | TB0145X | B008 | BJ | | | 277-299 |
| 633 | 24 | | PK | | 4-1 | 31-31-22 | D04819P | 43 | | | TB0145X | A162 | BJ | | | ALL |
| 638 | 24 | | PK | | 6-3 | 31-51-41 | TB0145D | A125 | 2 | | D04819P | 21 | | | | 150-199, 275-276 |
| 638 | 24 | | PK | | 3-3 | 31-51-41 | TB0145D | A096 | 2 | | D04819P | 21 | | | | 277-299 |
| 639 | 24 | | PK | | 3-2 | 31-51-41 | TB0145D | A125 | 2 | | TB0145D | A126 | 2 | | | 150-199, 275-276 |
| 639 | 24 | | PK | | 3-2 | 31-51-41 | TB0145D | A096 | 2 | | TB0145D | A097 | 2 | | | 277-299 |
| 640 | 24 | | PK | | 6-3 | 31-51-41 | TB0145D | C126 | 2 | | D04819P | 54 | | | | 150-199, 275-276 |
| 640 | 24 | | PK | | 3-3 | 31-51-41 | TB0145D | C097 | 2 | | D04819P | 54 | | | | 277-299 |
| 641 | 20 | | UA | | 1-6 | 34-61-24 | GDX0010 | S.. | 2 | | TB0145Y | REF | | | ZP | 157, 167-199, 275-276 |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 90
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | | |
| 641 | 20 | | UA | | 1-6 | 34-61-24 | GDX0002 | S.. | 2 | | | | TB0145Y | REF | | ZP | 277-299 |
| 641B | 24 | | PW | ZP | 2-11 | 34-61-24 | D00353B | B05 | | | | | TB0145Y | C077 | BJ | | 157, 167-199, 275-276 |
| 641B | 24 | | PW | ZP | 5-1 | 34-61-24 | D00353B | B05 | | | | | TB0145Y | C019 | BJ | | 277-299 |
| 641R | 24 | | PW | ZP | 0-0 | 34-61-24 | D00353B | A05 | | | | | TB0145Y | A077 | BJ | | 157, 167-199, 275-276 |
| 641R | 24 | | PW | ZP | 0-0 | 34-61-24 | D00353B | A05 | | | | | TB0145Y | A019 | BJ | | 277-299 |
| 641Z | | | | ZP | 0-0 | 34-61-24 | D00353B | DED | | | | | TB0145Y | REF | | ZP | 157, 167-199, 275-299 |
| 651 | 24 | | PK | | 4-6 | 34-53-22 | D00359A | C05 | | | | | TB0145Y | A074 | BJ | | 050-099, 155-164, 166-199, 275-299 |
| 651 | 24 | | PK | | 3-6 | 34-53-22 | TB0145G | 103 | 2 | | | | D00359A | C05 | | | 150-154 |
| 651 | 24 | | PK | | 4-6 | 34-53-22 | D00359A | C05 | | | | | TB0145Y | A074 | 2 | | 165 |
| 652 | 24 | | PK | | 3-2 | 34-61-26 | D02281 | X2 | | | | | TB0145Y | C168 | BJ | | ALL |
| 653 | 24 | | PK | | 4-2 | 34-61-26 | D04505P | 29 | | | | | TB0145Y | A148 | BJ | | ALL |
| 654 | 24 | | PK | | 3-10 | 34-61-26 | D02283 | X2 | | | | | TB0145Y | A044 | BJ | | ALL |
| 655 | 24 | | PK | | 4-6 | 31-31-22 | D05439P | 2 | | | | | TB0145X | C142 | BJ | | ALL |
| 656 | 22 | | PA | | 2-6 | 34-61-24 | D00353B | J15 | | | | | GDX0010 | D.. | 2 | | 050-099, 150-156, 162-199 |
| 656 | 22 | | PA | | 2-6 | 34-61-23 | D00353B | J15 | | | | | GDX0010 | D.. | 2 | | 157 |
| 657 | 24 | | PK | | 7-0 | 31-31-26 | D04339P | 21 | | | | | TB0145X | C107 | BJ | | 050-099 |
| 657 | 24 | | PK | | 6-11 | 31-31-26 | D04339P | 21 | | | | | TB0145X | C107 | BJ | | 150-199, 275-276 |
| 657 | 24 | | PK | | 6-9 | 31-31-26 | D04339P | 21 | | | | | TB0145X | C113 | BJ | | 277-299 |
| 658 | 24 | | PK | | 4-5 | 31-31-26 | D05715J | 35 | | | | | TB0145X | A105 | BJ | | 050-099 |
| 658 | 24 | | PK | | 4-3 | 31-31-26 | D05715J | 35 | | | | | TB0145X | A105 | BJ | | 150-199, 275-276 |
| 658 | 24 | | PK | | 4-3 | 31-31-26 | D05715J | 35 | | | | | TB0145X | A111 | BJ | | 277-299 |
| 659 | 24 | | PK | | 4-5 | 31-31-26 | D05715J | 36 | | | | | TB0145X | C105 | BJ | | 050-099 |
| 659 | 24 | | PK | | 4-3 | 31-31-26 | D05715J | 36 | | | | | TB0145X | C105 | BJ | | 150-199, 275-276 |
| 659 | 24 | | PK | | 4-3 | 31-31-26 | D05715J | 36 | | | | | TB0145X | C111 | BJ | | 277-299 |
| 660 | 24 | | PK | | 4-5 | 31-31-26 | D05715J | 37 | | | | | TB0145X | D105 | BJ | | 050-099 |
| 660 | 24 | | PK | | 4-3 | 31-31-26 | D05715J | 37 | | | | | TB0145X | D105 | BJ | | 150-199, 275-276 |
| 660 | 24 | | PK | | 4-3 | 31-31-26 | D05715J | 37 | | | | | TB0145X | D111 | BJ | | 277-299 |
| 662 | 24 | | PK | | 2-9 | 34-61-26 | D02283 | X1 | | | | | TB0145D | C093 | 2 | | 050-099, 155-199, 275-299 |
| 662 | 24 | | PK | | 3-4 | 34-61-26 | D02283 | X1 | | | | | TB0145Z | 65 | BJ | | 150-154 |
| 663 | 24 | | PK | | 2-9 | 34-61-26 | D02281 | X1 | | | | | TB0145D | C092 | 2 | | 050-099, 155-199, 275-277, 280-299 |
| 663 | 24 | | PK | | 3-3 | 34-61-26 | D02281 | X1 | | | | | TB0145Z | 65 | BJ | | 150-154 |
| 663 | 24 | | PK | | 2-11 | 34-61-26 | D02281 | X1 | | | | | TB0145D | C088 | 2 | | 278 |
| 664 | 24 | | PK | | 2-9 | 34-61-26 | D02277 | X1 | | | | | TB0145D | C094 | 2 | | 050-099, 155-199, 275-299 |
| 664 | 24 | | PK | | 3-3 | 34-61-26 | D02277 | X1 | | | | | TB0145Z | 65 | BJ | | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 91

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | | E2-3 R,SHELF (continued) | | | | | | | | | | |
| 665 | 24 | | PK | | 3-9 | 34-61-26 | D02277 | | X2 | | TB0145Y | A148 | BJ | | ALL |
| 666 | 24 | | PK | | 3-10 | 34-61-25 | D05439P | | 8 | | TB0145X | D169 | BJ | | ALL |
| 667 | 24 | | PK | | 4-6 | 34-53-22 | D00359B | | J05 | | TB0145Y | A074 | BJ | | 050-099, 155-164, 166-199, 275-299 |
| 667 | 24 | | PK | | 3-6 | 34-53-22 | D00359B | | J05 | | TB0145G | 103 | 2 | | 150-154 |
| 667 | 24 | | PK | | 4-6 | 34-53-22 | D00359B | | J05 | | TB0145Y | A074 | 2 | | 165 |
| 668 | 24 | | PK | | 4-6 | 34-53-22 | D00359A | | D05 | | TB0145Y | A074 | BJ | | 050-099, 155-164, 166-199, 275-299 |
| 668 | 24 | | PK | | 3-6 | 34-53-22 | D00359A | | D05 | | TB0145G | 103 | 2 | | 150-154 |
| 668 | 24 | | PK | | 4-6 | 34-53-22 | D00359A | | D05 | | TB0145Y | A074 | 2 | | 165 |
| 669 | 24 | | PK | | 4-3 | 34-53-21 | D00359B | | E06 | | TB0145Y | A168 | BJ | | 050-099, 155-199, 275-299 |
| 669 | 24 | | PK | | 4-9 | 34-53-21 | D00359B | | E06 | | TB0145Y | A168 | BJ | | 150-154 |
| 675B | 24 | | PW | C5 | 3-1 | 34-45-12 | D00359B | | F05 | | TB0145X | A119 | BJ | | 050-099, 155-156, 162-166 |
| 675B | 24 | | PW | C5 | 3-1 | 34-45-12 | D00359A | | F05 | | TB0145X | A119 | BJ | | 150-154, 157, 167-199 |
| 675B | 24 | | PW | C5 | 3-4 | 34-45-12 | D00359A | | F05 | | TB0145X | A119 | BJ | | 275-276 |
| 675B | 24 | | PW | C5 | 3-1 | 34-45-12 | D00359A | | F05 | | TB0145X | A124 | BJ | | 277-299 |
| 675R | 24 | | PW | C5 | 0-0 | 34-45-12 | D00359B | | E05 | | TB0145X | A118 | BJ | | 050-099, 155-156, 162-166 |
| 675R | 24 | | PW | C5 | 0-0 | 34-45-12 | D00359A | | E05 | | TB0145X | A118 | BJ | | 150-154, 157, 167-199, 275-276 |
| 675R | 24 | | PW | C5 | 0-0 | 34-45-12 | D00359A | | E05 | | TB0145X | A123 | BJ | | 277-299 |
| 675Z | | | | C5 | 0-0 | 34-45-12 | D00359B | | DED | | TB0145X | C118 | BJ | | 050-099, 155-156, 162-166 |
| 675Z | | | | C5 | 0-0 | 34-45-12 | D00359A | | DED | | TB0145X | C118 | BJ | | 150-154, 157, 167-199, 275-276 |
| 675Z | | | | C5 | 0-0 | 34-45-12 | D00359A | | DED | | TB0145X | C123 | BJ | | 277-299 |
| 676B | 24 | | PW | C6 | 3-1 | 34-45-12 | D00359B | | H05 | | TB0145X | B119 | BJ | | 050-099 |
| 676B | 24 | | PW | C6 | 3-1 | 34-45-12 | D00359A | | H05 | | TB0145X | B119 | BJ | | 150-152 |
| 676B | 24 | | PW | C6 | 3-1 | 34-45-12 | TB0145X | | B119 | BJ | D00359A | H05 | | | 153-154, 157, 167-199 |
| 676B | 24 | | PW | C6 | 3-1 | 34-45-12 | TB0145X | | B119 | BJ | D00359B | H05 | | | 155-156, 162-166 |
| 676B | 24 | | PW | C6 | 3-4 | 34-45-12 | D00359A | | H05 | | TB0145X | B119 | BJ | | 275-276 |
| 676B | 24 | | PW | C6 | 3-1 | 34-45-12 | D00359A | | H05 | | TB0145X | B124 | BJ | | 277-299 |
| 676R | 24 | | PW | C6 | 0-0 | 34-45-12 | D00359B | | G05 | | TB0145X | B118 | BJ | | 050-099 |
| 676R | 24 | | PW | C6 | 0-0 | 34-45-12 | D00359A | | G05 | | TB0145X | B118 | BJ | | 150-152, 275-276 |
| 676R | 24 | | PW | C6 | 0-0 | 34-45-12 | TB0145X | | B118 | BJ | D00359A | G05 | | | 153-154, 157, 167-199 |
| 676R | 24 | | PW | C6 | 0-0 | 34-45-12 | TB0145X | | B118 | BJ | D00359B | G05 | | | 155-156, 162-166 |
| 676R | 24 | | PW | C6 | 0-0 | 34-45-12 | D00359A | | G05 | | TB0145X | B123 | BJ | | 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 92
Aug 05/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 676Z | | | | C6 | 0-0 | 34-45-12 | D00359B | DED | | | | | TB0145X | C119 | BJ | 050-099 |
| 676Z | | | | C6 | 0-0 | 34-45-12 | D00359A | DED | | | | | TB0145X | C119 | BJ | 150-152, 275-276 |
| 676Z | | | | C6 | 0-0 | 34-45-12 | TB0145X | C119 | BJ | | | | D00359A | DED | | 153-154, 157, 167-199 |
| 676Z | | | | C6 | 0-0 | 34-45-12 | TB0145X | C119 | BJ | | | | D00359B | DED | | 155-156, 162-166 |
| 676Z | | | | C6 | 0-0 | 34-45-12 | D00359A | DED | | | | | TB0145X | C124 | BJ | 277-299 |
| 677 | 24 | | PK | | 4-2 | 34-61-16 | D05065P | 10 | | | | | TB0145Y | A140 | BJ | ALL |
| 678 | 24 | | PK | | 4-9 | 34-61-26 | D04433P | 8 | | | | | TB0145Y | A140 | BJ | ALL |
| 685B | 24 | | PW | D5 | 3-9 | 34-61-21 | D04433P | 3 | | | | | TB0145Y | C179 | BJ | ALL |
| 685R | 24 | | PW | D5 | 0-0 | 34-61-21 | D04433P | 2 | | | | | TB0145Y | A179 | BJ | ALL |
| 685Z | | | | D5 | 0-0 | 34-61-21 | D04433P | 1 | | | | | GDY0013 | S.. | 2 | 050-099, 150-199, 275-276 |
| 685Z | | | | D5 | 0-0 | 34-61-21 | D04433P | 1 | | | | | GDY0012 | S.. | 2 | 277-299 |
| 686 | 24 | | PK | | 3-9 | 34-61-15 | D00353B | G15 | | | | | TB0145X | B047 | BJ | 050-099, 150-199, 275-276 |
| 686 | 24 | | PK | | 2-11 | 34-61-15 | D00353B | G15 | | | | | TB0145X | B083 | BJ | 277-299 |
| 687 | 24 | | PK | | 4-3 | 34-61-15 | D00353B | A11 | | | | | TB0145Y | A032 | BJ | ALL |
| 688 | 24 | | PK | | 4-3 | 34-61-15 | D00353A | K08 | | | | | TB0145Y | A032 | BJ | ALL |
| 689 | 24 | | PK | | 4-1 | 34-61-26 | D04899P | 6 | | | | | D00353B | CAP | Y | 050-099, 155-156, 162-166 |
| 689 | 24 | | PK | | 4-1 | 34-61-26 | D04899P | 6 | | | | | D00353B | J09 | | 157, 275-299 |
| 689 | 24 | | PK | | 4-1 | 34-61-26 | D04899P | 6 | | | | | D00353B | REF | ** | 167-199 |
| 690 | 24 | | PK | | 4-1 | 34-61-16 | D04899P | 16 | | | | | D00353B | CAP | Y | 050-099, 155-156, 162-166 |
| 690 | 24 | | PK | | 4-1 | 34-61-16 | D04899P | 16 | | | | | D00353B | K09 | | 157, 275-299 |
| 690 | 24 | | PK | | 4-1 | 34-61-16 | D04899P | 16 | | | | | D00353B | REF | ** | 167-199 |
| 691 | 24 | | PK | | 3-11 | 34-61-26 | TB0145D | A093 | 2 | | | | TB0145Z | 65 | BJ | 050-099 |
| 691 | 24 | | PK | | 3-11 | 34-61-26 | TB0145Z | 65 | BJ | | | | TB0145D | A093 | 2 | 155-199, 275-299 |
| 692 | 24 | | PK | | 3-11 | 34-61-26 | TB0145D | A092 | 2 | | | | TB0145Z | 65 | BJ | 050-099 |
| 692 | 24 | | PK | | 3-11 | 34-61-26 | TB0145Z | 65 | BJ | | | | TB0145D | A092 | 2 | 155-199, 275-277, 280-299 |
| 692 | 24 | | PK | | 3-4 | 34-61-26 | TB0145Z | 65 | BJ | | | | TB0145D | A088 | 2 | 278 |
| 693 | 24 | | PK | | 3-11 | 34-61-26 | TB0145D | A094 | 2 | | | | TB0145Z | 65 | BJ | 050-099 |
| 693 | 24 | | PK | | 3-11 | 34-61-26 | TB0145Z | 65 | BJ | | | | TB0145D | A094 | 2 | 155-199, 275-299 |
| 695 | 24 | | PK | | 5-3 | 34-61-24 | D00353A | K06 | | | | | TB0145Y | A112 | BJ | 050-099 |
| 695 | 24 | | PK | | 5-2 | 34-61-24 | D00353A | K06 | | | | | TB0145Y | A112 | BJ | 155-199, 276 |
| 695 | 24 | | PK | | 5-1 | 34-61-24 | D00353A | K06 | | | | | TB0145Y | A118 | BJ | 277-299 |
| 696B | 24 | | PW | F6 | 3-5 | 31-35-15 | TB0145X | B089 | BJ | | | | D04667P | 34 | | 050-099, 150-199, 275-276 |
| 696B | 24 | | PW | F6 | 4-7 | 31-35-15 | TB0145X | C038 | BJ | | | | D04667P | 34 | | 278-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 93

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 696R | 24 | PW | F6 | 0-0 | 31-35-15 | TB0145X | A089 | BJ | | D04667P | 33 | | | 050-099, 150-199, 275-276 | |
| 696R | 24 | PW | F6 | 0-0 | 31-35-15 | TB0145X | D038 | BJ | | D04667P | 33 | | | 278-299 | |
| 696Z | | | F6 | 0-0 | 31-35-15 | GDY0013 | S.. | 2 | | D04667P | 35 | | | 050-099, 150-199, 275-276 | |
| 696Z | | | F6 | 0-0 | 31-35-15 | GDY0006 | S.. | 2 | | D04667P | 35 | | | 278 | |
| 696Z | | | F6 | 0-0 | 31-35-15 | GDY0007 | S.. | 2 | | D04667P | 35 | | | 280-299 | |
| 697 | 24 | PK | | 6-1 | 34-53-21 | D04697P | | 13 | | D00359A | B03 | | | 050-099, 150-152, 155-199, 275-299 | |
| 699 | 24 | PK | | 3-8 | 34-45-13 | D05065P | | 15 | | D04767P | 36 | | | ALL | |
| 704 | 20 | UA | | 1-6 | 34-45-14 | GDX0001 | S.. | 2 | | TB0145Y | REF | | G4 | 050-099 | |
| 704 | 20 | UA | | 3-0 | 34-45-14 | GDX0001 | S.. | 2 | | TB0145Y | REF | | G4 | 153-156, 162-166 | |
| 704 | 20 | UA | | 1-6 | 34-45-14 | GDX0011 | S.. | 2 | | TB0145Z | REF | | G4 | 275-276 | |
| 704B | 24 | PW | G4 | 5-4 | 34-45-14 | D04767P | | 55 | | TB0145Y | C007 | BJ | | 050-099, 153-156, 162-166 | |
| 704B | 24 | PW | G4 | 4-11 | 34-45-14 | D04767P | | 55 | | TB0145G | 25 | 2 | | 150-152 | |
| 704B | 24 | PW | G4 | 2-11 | 34-45-14 | D04767P | | 55 | | TB0145Z | 182 | BJ | | 275-276 | |
| 704R | 24 | PW | G4 | 0-0 | 34-45-14 | D04767P | | 54 | | TB0145Y | A007 | BJ | | 050-099, 153-156, 162-166 | |
| 704R | 24 | PW | G4 | 0-0 | 34-45-14 | D04767P | | 54 | | TB0145G | 24 | 2 | | 150-152 | |
| 704R | 24 | PW | G4 | 0-0 | 34-45-14 | D04767P | | 54 | | TB0145Z | 181 | BJ | | 275-276 | |
| 704Z | | | G4 | 0-0 | 34-45-14 | D04767P | | 19 | | TB0145Y | REF | | G4 | 050-099, 155-156, 162-166 | |
| 704Z | | | G4 | 0-0 | 34-45-14 | D04767P | | 19 | | GDY0002 | S.. | 2 | | 150-152 | |
| 704Z | | | G4 | 0-0 | 34-45-14 | D04767P | | 27 | | TB0145Y | REF | | G4 | 153-154 | |
| 704Z | | | G4 | 0-0 | 34-45-14 | D04767P | | 19 | | TB0145Z | REF | | G4 | 275-276 | |
| 709 | 20 | UA | | 1-6 | 34-61-25 | GDX0011 | S.. | 2 | | TB0145Y | REF | | G9 | 157, 167-199 | |
| 709 | 20 | UA | | 1-6 | 34-61-25 | GDX0002 | S.. | 2 | | TB0145Y | REF | | G9 | 275-299 | |
| 709B | 24 | PW | G9 | 2-10 | 34-61-25 | D00353B | H09 | ** | | TB0145Y | C180 | BJ | | 157 | |
| 709B | 24 | PW | G9 | 2-10 | 34-61-25 | D00353B | REF | ** | | TB0145Y | C180 | BJ | | 167-199 | |
| 709B | 24 | PW | G9 | 5-1 | 34-61-25 | D00353B | H09 | ** | | TB0145Y | C020 | BJ | | 275-299 | |
| 709R | 24 | PW | G9 | 0-0 | 34-61-25 | D00353B | G09 | ** | | TB0145Y | A180 | BJ | | 157 | |
| 709R | 24 | PW | G9 | 0-0 | 34-61-25 | D00353B | REF | ** | | TB0145Y | A180 | BJ | | 167-199 | |
| 709R | 24 | PW | G9 | 0-0 | 34-61-25 | D00353B | G09 | ** | | TB0145Y | A020 | BJ | | 275-299 | |
| 709Z | | | G9 | 0-0 | 34-61-25 | D00353B | DED | | | TB0145Y | REF | | G9 | 157, 167-199, 275-299 | |
| 714 | 24 | PK | | 3-6 | 34-61-27 | D00353A | K15 | | | TB0145D | C197 | 2 | | 157, 167-199, 277-299 | |
| 715 | 20 | UA | | 1-6 | 34-61-27 | TB0145Z | REF | | H5 | GDX0011 | S.. | 2 | | 157, 167-199, 275-276 | |
| 715 | 20 | UA | | 1-6 | 34-61-27 | TB0145Z | REF | | H5 | GDX0003 | S.. | 2 | | 277-299 | |
| 715B | 24 | PW | H5 | 3-10 | 34-61-27 | TB0145Z | | 182 | BJ | D02819 | B3 | | | 157, 167-199 | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 94

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|-----------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 715B | 24 | PW | H5 | 3-10 | 34-61-27 | TB0145Z | 184 | BJ | | D02819 | B3 | | | 275-276 | | |
| 715B | 24 | PW | H5 | 2-10 | 34-61-27 | TB0145Z | 126 | BJ | | D02819 | B3 | | | 277-299 | | |
| 715R | 24 | PW | H5 | 0-0 | 34-61-27 | TB0145Z | 181 | BJ | | D02819 | A3 | | | 157, 167-199 | | |
| 715R | 24 | PW | H5 | 0-0 | 34-61-27 | TB0145Z | 183 | BJ | | D02819 | A3 | | | 275-276 | | |
| 715R | 24 | PW | H5 | 0-0 | 34-61-27 | TB0145Z | 125 | BJ | | D02819 | A3 | | | 277-299 | | |
| 715Z | | | H5 | 0-0 | 34-61-27 | TB0145Z | REF | | H5 | D02819 | DED | | | 157, 167-199, 275-299 | | |
| 716 | 20 | UA | | 1-6 | 34-61-27 | TB0145Y | REF | | H6 | GDX0001 | S.. | 2 | | 157, 167-199 | | |
| 716 | 20 | UA | | 1-6 | 34-61-27 | TB0145Z | REF | | H6 | GDX0011 | S.. | 2 | | 275-276 | | |
| 716 | 20 | UA | | 1-6 | 34-61-27 | TB0145Z | REF | | H6 | GDX0003 | S.. | 2 | | 277-299 | | |
| 716B | 24 | PW | H6 | 3-4 | 34-61-27 | TB0145Y | C007 | BJ | | D02819 | B1 | | | 157, 167-199 | | |
| 716B | 24 | PW | H6 | 3-10 | 34-61-27 | TB0145Z | 182 | BJ | | D02819 | B1 | | | 275-276 | | |
| 716B | 24 | PW | H6 | 2-11 | 34-61-27 | TB0145Z | 24 | BJ | | D02819 | B1 | | | 277-299 | | |
| 716R | 24 | PW | H6 | 0-0 | 34-61-27 | TB0145Y | A007 | BJ | | D02819 | A1 | | | 157, 167-199 | | |
| 716R | 24 | PW | H6 | 0-0 | 34-61-27 | TB0145Z | 181 | BJ | | D02819 | A1 | | | 275-276 | | |
| 716R | 24 | PW | H6 | 0-0 | 34-61-27 | TB0145Z | 23 | BJ | | D02819 | A1 | | | 277-299 | | |
| 716Z | | | H6 | 0-0 | 34-61-27 | TB0145Y | REF | | H6 | D02819 | DED | | | 157, 167-199 | | |
| 716Z | | | H6 | 0-0 | 34-61-27 | TB0145Z | REF | | H6 | D02819 | DED | | | 275-299 | | |
| 717 | 24 | PK | | 4-1 | 34-61-27 | TB0145X | C089 | ** | | D02819 | X1 | | | 157 | | |
| 717 | 24 | PK | | 4-1 | 34-61-27 | TB0145X | C089 | % | | D02819 | X1 | | | 167-199 | | |
| 717 | 24 | PK | | 3-4 | 34-61-27 | TB0145X | A008 | BJ | | D02819 | X1 | | | 275-299 | | |
| 718 | 24 | PK | | 4-1 | 34-61-27 | TB0145D | A088 | 2 | | D02819 | X2 | | | 157, 167-199 | | |
| 718 | 24 | PK | | 4-1 | 34-61-27 | TB0145D | A089 | 2 | | D02819 | X2 | | | 275-299 | | |
| 719 | 24 | PK | | 3-0 | 34-61-27 | TB0145D | C088 | 2 | | D00353B | K04 | | | 157, 167-199 | | |
| 719 | 24 | PK | | 3-0 | 34-61-27 | TB0145D | C089 | 2 | | D00353B | K04 | | | 275-299 | | |
| 720 | 24 | PK | | 2-11 | 34-61-27 | TB0145Y | A078 | BJ | | D00353B | K13 | ** | | 157 | | |
| 720 | 24 | PK | | 2-11 | 34-61-27 | TB0145Y | A078 | BJ | | D00353B | REF | ** | | 167-199 | | |
| 720 | 24 | PK | | 5-3 | 34-61-27 | TB0145Y | C012 | BJ | | D00353B | K13 | | | 277-299 | | |
| 721 | 24 | PK | | 2-11 | 34-61-27 | D00353B | K06 | | | TB0145D | C189 | 2 | | 157, 167-199, 275-299 | | |
| 722 | 20 | UA | | 1-6 | 34-22-91 | GDX0003 | S.. | 2 | | D02819 | REF | | I2 | 157, 167-199, 280-299 | | |
| 722 | 20 | UA | | 2-0 | 34-22-91 | GDX0003 | S.. | 2 | | D02819 | REF | | I2 | 275-276 | | |
| 722 | 20 | UA | | 3-9 | 34-22-91 | GDX0013 | S.. | 2 | | D02819 | REF | | I2 | 277-278 | | |
| 722B | 24 | PW | I2 | 5-2 | 34-22-91 | D04899P | 28 | | | D02819 | B2 | | | 157, 167-199, 275-299 | | |
| 722R | 24 | PW | I2 | 0-0 | 34-22-91 | D04899P | 27 | | | D02819 | A2 | | | 157, 167-199, 275-299 | | |
| 722Z | | | I2 | 0-0 | 34-22-91 | D04899P | 29 | | | D02819 | REF | | I2 | 157, 167-199, 275-299 | | |
| 724 | 20 | PA | | 2-1 | 34-53-21 | D00359C | 8 | | | GDX0003 | D.. | 2 | | 157, 167-199, 277-299 | | |
| 725 | 24 | PK | | 3-10 | 27-81-31 | D04819P | 23 | | | D05715J | 3 | | | 150-199, 275-299 | | |
| 726B | 24 | PW | I6 | 3-9 | 34-61-25 | TB0145Y | C133 | BJ | | TB0145Y | C020 | BJ | | 157 | | |
| 726B | 24 | PW | I6 | 4-0 | 34-61-25 | TB0145Y | C133 | BJ | | TB0145Y | C180 | BJ | | 167-199 | | |
| 726R | 24 | PW | I6 | 0-0 | 34-61-25 | TB0145Y | A133 | BJ | | TB0145Y | A020 | BJ | | 157 | | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 95

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 726R | 24 | PW | I6 | 0-0 | 34-61-25 | TB0145Y | A133 | BJ | | TB0145Y | A180 | BJ | | 167-199 | | |
| 726Z | | | I6 | 0-0 | 34-61-25 | GDY0006 | S.. | 2 | | TB0145Y | DED | | | 157, 167-199 | | |
| 730B | 24 | PW | J0 | 5-4 | 22-21-31 | D06261P | | 2 | | D05407P | 13 | | | 167-199, 275-299 | | |
| 730R | 24 | PW | J0 | 0-0 | 22-21-31 | D06261P | | 1 | | D05407P | 12 | | | 167-199, 275-299 | | |
| 730Z | | | J0 | 0-0 | 22-21-31 | D06261P | | 3 | | D05407P | 14 | | | 167-199, 275-299 | | |
| 749 | 24 | PK | | 3-2 | 34-12-62 | D03693P | | 8 | | TB0145Y | A194 | BJ | | 050-099, 152 | | |
| 749 | 24 | PK | | 3-2 | 34-12-62 | D03693P | | 8 | | TB0145Y | A185 | BJ | | 150-151, 153-199, 275-299 | | |
| 750 | 24 | PK | | 3-2 | 34-12-62 | D03693P | | 9 | | TB0145Y | C194 | BJ | | 050-099, 152 | | |
| 750 | 24 | PK | | 3-2 | 34-12-62 | D03693P | | 9 | | TB0145Y | C185 | BJ | | 150-151, 153-199, 275-299 | | |
| 751 | 24 | PK | | 3-2 | 34-12-62 | D03693P | | 7 | | TB0145Y | A186 | BJ | | ALL | | |
| 800 | 24 | PK | | 4-0 | 31-31-26 | D04697P | | 4 | | TB0145R | A073 | 2 | | 050-099, 150-199, 275-276 | | |
| 800 | 24 | PK | | 3-9 | 31-31-26 | D04697P | | 4 | | TB0145R | A091 | 2 | | 277-299 | | |
| 801 | 20 | PQ | Q1 | 4-11 | 34-12-21 | TB0145Y | C031 | BJ | | D00351C | 1 | | | ALL | | |
| 801Z | | | Q1 | 0-0 | 34-12-21 | TB0145Y | DED | | | D00351C | DED | | | ALL | | |
| 803 | 24 | PK | | 4-9 | 34-12-22 | D04505P | | 31 | | TB0145Y | A031 | BJ | | ALL | | |
| 806 | 22 | PA | | 0-7 | 34-12-22 | D00351B | D14 | | | D00351B | K14 | | | 050-099 | | |
| 806 | 22 | PA | | 0-7 | 34-12-22 | D00351B | D14 | | | D00351B | G14 | | | 150-199, 275-299 | | |
| 807 | 16 | PA | | 4-9 | 34-12-21 | GDY0007 | A.. | 2 | | D00351C | 7 | | | ALL | | |
| 808 | 16 | PA | | 4-9 | 34-12-21 | GDY0007 | D.. | 2 | | D00351C | 8 | | | ALL | | |
| 811 | 22 | PA | | 2-4 | 34-12-22 | GDX0014 | D.. | 2 | | D00351B | J06 | | | ALL | | |
| 812 | 24 | PK | | 3-11 | 34-12-22 | D04667P | | 17 | | D00351B | F02 | | | ALL | | |
| 813 | 24 | PK | | 3-11 | 34-12-22 | D04667P | | 16 | | D00351B | E10 | | | ALL | | |
| 818 | 24 | PK | | 3-11 | 34-12-22 | D04667P | | 19 | | D00351B | F09 | | | ALL | | |
| 821 | 24 | PK | | 3-11 | 34-12-22 | D04667P | | 20 | | D00351B | F10 | | | ALL | | |
| 823 | 22 | PA | | 4-2 | 34-12-22 | TB0145Z | | 59 | BJ | D00351B | F15 | | | ALL | | |
| 824 | 22 | PA | | 2-4 | 34-12-22 | GDX0014 | S.. | 2 | | D00351B | D07 | | | ALL | | |
| 825 | 22 | PA | | 4-2 | 34-12-22 | TB0145Z | | 59 | BJ | D00351B | G15 | | | ALL | | |
| 827 | 24 | PV | S7 | 4-1 | 34-12-12 | TB0145X | B158 | BJ | | D00351B | F11 | | | ALL | | |
| 827Z | | | S7 | 0-0 | 34-12-12 | TB0145X | DED | | | D00351B | DED | | | ALL | | |
| 830 | 22 | PQ | T0 | 5-1 | 34-12-21 | TB0145Y | C031 | BJ | | D04253P | 7 | | | ALL | | |
| 830Z | | | T0 | 0-0 | 34-12-21 | TB0145Y | DED | | | D04253P | DED | | | ALL | | |
| 831 | 22 | PQ | T1 | 4-10 | 34-12-21 | TB0145Z | | 35 | BJ | D04253P | 9 | | | ALL | | |
| 831Z | | | T1 | 0-0 | 34-12-21 | TB0145Z | DED | | | D04253P | DED | | | ALL | | |
| 832 | 22 | PQ | T2 | 4-10 | 34-12-21 | TB0145Z | | 36 | BJ | D04253P | 8 | | | ALL | | |
| 832Z | | | T2 | 0-0 | 34-12-21 | TB0145Z | DED | | | D04253P | DED | | | ALL | | |
| 833 | 22 | PQ | T3 | 4-2 | 34-12-21 | D04667P | | 14 | | D04253P | 10 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 96

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 833Z | | | T3 | 0-0 | 34-12-21 | D04667P | | DED | | | | D04253P | DED | | | ALL |
| 834 | 22 | PQ | T4 | 4-10 | 34-12-21 | D04667P | | 13 | | | | TB0145Y | C031 | BJ | | ALL |
| 834Z | | | T4 | 0-0 | 34-12-21 | D04667P | | DED | | | | TB0145Y | DED | | | ALL |
| 835 | 22 | PA | | 4-9 | 34-12-21 | D04667P | | 15 | | | | GDY0007 | A.. | 2 | | ALL |
| 838 | 24 | PK | | 3-10 | 27-32-11 | D05715J | | 8 | | | | D04819P | 24 | | | ALL |
| 839 | 24 | PK | | 3-10 | 27-32-11 | D05715J | | 9 | | | | D04819P | 36 | | | ALL |
| 840 | 24 | PK | | 3-10 | 27-32-11 | D05715J | | 10 | | | | D04819P | 37 | | | ALL |
| 841 | 24 | PK | | 3-10 | 27-32-11 | D05715J | | 11 | | | | D04819P | 38 | | | ALL |
| 842 | 24 | PK | | 3-10 | 27-32-21 | D05715J | | 12 | | | | D04819P | 39 | | | ALL |
| 843 | 24 | PK | | 3-10 | 27-32-21 | D05715J | | 13 | | | | D04819P | 40 | | | ALL |
| 844 | 24 | PK | | 3-10 | 27-32-21 | D05715J | | 14 | | | | D04819P | 35 | | | ALL |
| 845 | 24 | PK | | 3-10 | 27-32-21 | D05715J | | 15 | | | | D04819P | 41 | | | ALL |
| 847 | 24 | PK | | 3-5 | 34-61-25 | D05713P | | 54 | | | | TB0145Y | A155 | BJ | | ALL |
| 848 | 24 | PK | | 3-3 | 34-21-21 | D04767P | | 37 | | | | TB0145Y | A168 | BJ | | ALL |
| 849 | 24 | PK | | 4-0 | 31-31-19 | TB0145X | | A042 | BJ | | | D04449P | 6 | | | ALL |
| 850 | 22 | PA | | 4-2 | 34-12-22 | D00351B | | F05 | | | | TB0145Z | 59 | BJ | | ALL |
| 854 | 24 | PK | | 4-0 | 31-31-19 | TB0145X | | B042 | BJ | | | D04449P | 7 | | | ALL |
| 855 | 22 | PA | | 4-2 | 34-12-22 | D00351B | | D02 | | | | TB0145Z | 59 | BJ | | ALL |
| 856 | 22 | PA | | 4-2 | 34-12-22 | D00351B | | G03 | | | | TB0145Z | 59 | BJ | | ALL |
| 857 | 24 | PK | | 4-11 | 34-12-22 | D00351B | | E03 | | | | TB0145Y | C136 | BJ | | 050-099 |
| 857 | 24 | PK | | 4-11 | 34-12-22 | D00351B | | E03 | | | | TB0145Y | C032 | BJ | | 150-151, 153-199, 275-299 |
| 857 | 24 | PK | | 4-11 | 34-12-22 | D00351B | | E03 | | | | TB0145Y | C030 | BJ | | 152 |
| 858 | 24 | PK | | 4-6 | 34-12-22 | D05065P | | 29 | | | | TB0145Y | A031 | BJ | | ALL |
| 859 | 24 | PK | | 5-2 | 31-51-21 | D04819P | | 9 | | | | TB0145Y | A031 | BJ | | ALL |
| 861 | 24 | PK | | 6-1 | 31-41-16 | D05065P | | 31 | | | | TB0145Y | A008 | BJ | | 050-099, 150-199, 275-276 |
| 861 | 24 | PK | | 5-4 | 31-41-16 | D05065P | | 31 | | | | TB0145Y | A014 | BJ | | 277-299 |
| 862 | 24 | PK | | 6-9 | 31-51-33 | D04819P | | 13 | | | | TB0145Y | A008 | BJ | | 050-099, 150-199, 275-276 |
| 862 | 24 | PK | | 6-6 | 31-51-33 | D04819P | | 13 | | | | TB0145Y | A014 | BJ | | 277-299 |
| 863 | 24 | PK | | 3-11 | 31-41-16 | D05065P | | 30 | | | | D04819P | 15 | | | ALL |
| 865 | 22 | PA | | 4-2 | 34-12-22 | D00351B | | K15 | | | | TB0145Z | 59 | BJ | | 050-099 |
| 866 | 24 | PK | | 3-0 | 34-61-25 | TB0145D | | A076 | 2 | | | TB0145Z | 65 | BJ | | 050-099, 150-199, 275-276 |
| 866 | 24 | PK | | 3-4 | 34-61-25 | TB0145D | | A190 | 2 | | | TB0145Z | 65 | BJ | | 277-299 |
| 874 | 22 | PA | | 2-5 | 34-61-23 | D00353B | | K14 | | | | GDY0012 | D.. | 2 | | 157, 167-199, 275-299 |
| 878 | 24 | PK | | 6-1 | 34-53-21 | D00359A | | K05 | | | | D04697P | 16 | | | 157, 167-199, 277-299 |
| 882 | 24 | PK | | 3-9 | 34-12-62 | D03693P | | 10 | | | | TB0145Y | A031 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 97

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0145 | 286T0145 | | | | E2-3 R,SHELF (continued) | | | | | | | | | | | |
| 884 | 24 | | PK | | 3-9 | 34-12-62 | D03693P | | 11 | | | | TB0145Y | C136 | BJ | 050-099 |
| 884 | 24 | | PK | | 3-9 | 34-12-62 | D03693P | | 11 | | | | TB0145Y | C032 | BJ | 150-151, 153-199, 275-299 |
| 884 | 24 | | PK | | 3-9 | 34-12-62 | D03693P | | 11 | | | | TB0145Y | C030 | BJ | 152 |
| 885 | 22 | | PA | | 3-4 | 34-12-62 | D04505P | | 19 | | | | D03693P | 6 | | 050-099, 150-199, 280-299 |
| 885 | 22 | | PA | | 3-4 | 34-12-62 | D03693P | | 6 | | | | D04505P | 19 | | 275-278 |
| 896 | 22 | | PA | | 3-8 | 34-12-62 | D03693P | | 1 | | | | TB0145D | A090 | 2 | 050-099, 162-166 |
| 896 | 22 | | PA | | 3-8 | 34-12-62 | D03693P | | 1 | | | | TB0145D | A184 | 2 | 150-151, 153-156, 277-299 |
| 896 | 22 | | PA | | 3-8 | 34-12-62 | D03693P | | 1 | | | | TB0145D | A092 | 2 | 152 |
| 896 | 22 | | PA | | 3-8 | 34-12-62 | D03693P | | 1 | | | | TB0145D | A091 | 2 | 157, 167-199 |
| 896 | 22 | | PA | | 3-8 | 34-12-62 | D03693P | | 1 | | | | TB0145D | A190 | 2 | 275-276 |
| 897 | 22 | | PA | | 3-8 | 34-12-62 | D03693P | | 2 | | | | TB0145D | C090 | 2 | 050-099, 162-166 |
| 897 | 22 | | PA | | 3-8 | 34-12-62 | D03693P | | 2 | | | | TB0145D | C184 | 2 | 150-151, 153-156, 277-299 |
| 897 | 22 | | PA | | 3-8 | 34-12-62 | D03693P | | 2 | | | | TB0145D | C092 | 2 | 152 |
| 897 | 22 | | PA | | 3-8 | 34-12-62 | D03693P | | 2 | | | | TB0145D | C091 | 2 | 157, 167-199 |
| 897 | 22 | | PA | | 3-8 | 34-12-62 | D03693P | | 2 | | | | TB0145D | C190 | 2 | 275-276 |
| 898 | 20 | | PA | | 2-3 | 34-12-62 | TB0145D | A090 | 2 | | | | GDX0012 | D.. | 2 | 050-099, 162-166 |
| 898 | 20 | | PA | | 2-3 | 34-12-62 | TB0145D | A184 | 2 | | | | GDX0012 | D.. | 2 | 150-151, 153-156, 277-299 |
| 898 | 20 | | PA | | 2-3 | 34-12-62 | TB0145D | A092 | 2 | | | | GDX0012 | D.. | 2 | 152 |
| 898 | 20 | | PA | | 2-3 | 34-12-62 | TB0145D | A091 | 2 | | | | GDX0012 | D.. | 2 | 157, 167-199 |
| 898 | 20 | | PA | | 2-3 | 34-12-62 | TB0145D | A190 | 2 | | | | GDX0012 | D.. | 2 | 275-276 |
| 900 | 20 | | PA | | 4-0 | 34-53-21 | D00359A | | | | | AA | GDX0003 | S.. | 2 | 275-278 |
| 900 | 20 | | PA | | 4-0 | 34-53-21 | D00359A | | | | | AE | GDX0003 | S.. | 2 | 280-299 |
| 901 | 20 | | PA | | 4-0 | 34-53-21 | D00359B | G05 | DL | | | | GDX0003 | D.. | 2 | 275-299 |
| 902 | 20 | | PA | | 3-0 | 34-53-21 | D00359A | | | | | AC | GDX0003 | S.. | 2 | 275-278 |
| 902 | 20 | | PA | | 3-0 | 34-53-21 | D00359A | | | | | AH | GDX0003 | S.. | 2 | 280-299 |
| 902B | 24 | | PW | A | 0-0 | 23-22-11 | TB0145Z | | 182 | BJ | | | D04811P | 54 | | 275-276 |
| 902B | 24 | | PW | A | 0-0 | 23-22-11 | TB0145Z | | 24 | BJ | | | D04811P | 54 | | 277-299 |
| 902R | 24 | | PW | A | 10-0 | 23-22-11 | TB0145Z | | 181 | BJ | | | D04811P | 53 | | 275-276 |
| 902R | 24 | | PW | A | 10-0 | 23-22-11 | TB0145Z | | 23 | BJ | | | D04811P | 53 | | 277-299 |
| 902Z | | | | A | 0-0 | 23-22-11 | GDX0003 | | S.. | 2 | | | D04811P | 55 | | 275-299 |
| 903 | 20 | | PA | | 3-0 | 34-53-21 | D00359A | | | | | AB | GDX0003 | S.. | 2 | 275-278 |
| 903 | 20 | | PA | | 3-0 | 34-53-21 | D00359A | | | | | AG | GDX0003 | S.. | 2 | 280-299 |
| 903B | 24 | | PW | AC | 0-0 | 34-53-21 | D00359A | | B06 | | | | TB0145Z | 182 | BJ | 275-276 |
| 903B | 24 | | PW | AC | 0-0 | 34-53-21 | D00359A | | B06 | | | | TB0145Z | 24 | BJ | 277-278 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 98

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0145 | 286T0145 | | | E2-3 R,SHELF (continued) | | | | | | | | | | | | |
| 903B | 24 | PW | AV | | 0-0 | 34-53-21 | D00359A | | B06 | | | TB0145Z | 24 | BJ | | 280-299 |
| 903R | 24 | PW | AC | | 10-0 | 34-53-21 | D00359A | | A06 | | | TB0145Z | 181 | BJ | | 275-276 |
| 903R | 24 | PW | AC | | 10-0 | 34-53-21 | D00359A | | A06 | | | TB0145Z | 23 | BJ | | 277-278 |
| 903R | 24 | PW | AV | | 10-0 | 34-53-21 | D00359A | | A06 | | | TB0145Z | 23 | BJ | | 280-299 |
| 903Z | | | AC | | 0-0 | 34-53-21 | D00359A | | | | AA | GDX0003 | S.. | 2 | | 275-278 |
| 903Z | | | AV | | 0-0 | 34-53-21 | D00359A | | | | AE | GDX0003 | S.. | 2 | | 280-299 |
| 904B | 24 | PW | AE | | 0-0 | 34-53-21 | D00359A | | D02 | | | D04667P | 39 | | | 275-278 |
| 904B | 24 | PW | BB | | 0-0 | 34-53-21 | D00359A | | D02 | | | D04667P | 39 | | | 280-299 |
| 904R | 24 | PW | AE | | 5-0 | 34-53-21 | D00359A | | C02 | | | D04667P | 38 | | | 275-278 |
| 904R | 24 | PW | BB | | 5-0 | 34-53-21 | D00359A | | C02 | | | D04667P | 38 | | | 280-299 |
| 904Z | | | AE | | 0-0 | 34-53-21 | D00359A | | | | AC | D04667P | 40 | | | 275-278 |
| 904Z | | | BB | | 0-0 | 34-53-21 | D00359A | | | | AH | D04667P | 40 | | | 280-299 |
| 913B | 24 | PW | AD | | 0-0 | 34-53-21 | D00359A | | B07 | | | D04679P | 8 | | | 275-278 |
| 913B | 24 | PW | AX | | 0-0 | 34-53-21 | D00359A | | B07 | | | D04679P | 8 | | | 280-299 |
| 913R | 24 | PW | AD | | 5-0 | 34-53-21 | D00359A | | A07 | | | D04679P | 7 | | | 275-278 |
| 913R | 24 | PW | AX | | 5-0 | 34-53-21 | D00359A | | A07 | | | D04679P | 7 | | | 280-299 |
| 913Z | | | AD | | 0-0 | 34-53-21 | D00359A | | | | AB | D04679P | 9 | | | 275-278 |
| 913Z | | | AX | | 0-0 | 34-53-21 | D00359A | | | | AG | D04679P | 9 | | | 280-299 |
| W0146 | 286T0146 | | | P33-S2-MISC ELECTRICAL PANEL | | | | | | | | | | | | |
| 001 | 24 | PK | | | 4-0 | 24-31-11 | D04042J | | 1 | | | TB0186X | A001 | BJ | | ALL |
| 002 | 24 | PK | | | 4-0 | 24-31-11 | D04042J | | 2 | | | TB0186X | B001 | BJ | | ALL |
| 004 | 24 | PK | | | 4-0 | 28-25-11 | TB0188X | | B006 | BJ | | D04042J | 4 | | | ALL |
| 011 | 24 | PK | | | 4-0 | 28-22-11 | TB0188X | | A006 | BJ | | D04042J | 3 | | | ALL |
| 061 | 22 | PA | | | 4-0 | 30-34-11 | D04042J | | 20 | | | TB0188X | C020 | BJ | | ALL |
| 062 | 22 | PQ | AD | | 4-0 | 28-42-12 | D04042J | | 18 | | | TB0186Y | A011 | BJ | | 050-099 |
| 062 | 22 | PQ | AB | | 4-0 | 28-42-12 | D04042J | | 18 | | | TB0186Y | A011 | BJ | | 155-199, 276-299 |
| 062Z | | | AD | | 0-0 | 28-42-12 | D04042J | | DED | | | TB0186Y | DED | | | 050-099 |
| 062Z | | | AB | | 0-0 | 28-42-12 | D04042J | | DED | | | TB0186Y | DED | | | 155-199, 276-299 |
| 064 | 20 | PQ | CN | | 6-0 | 78-34-21 | D04042J | | 22 | | | TB0460Y | C005 | BJ | | ALL |
| 064Z | | | CN | | 0-0 | 78-34-21 | D04042J | | DED | | | TB0460Y | DED | | | ALL |
| 065 | 20 | PQ | CO | | 4-0 | 78-34-11 | D04042J | | 21 | | | TB0458Y | C005 | BJ | | ALL |
| 065Z | | | CO | | 0-0 | 78-34-11 | D04042J | | DED | | | TB0458Y | DED | | | ALL |
| 16A | 22 | PQ | ZA | | 8-0 | 28-42-12 | D04042J | | 23 | | | TB0186Y | A011 | BJ | | 150-154, 275 |
| 16AZ | | | ZA | | 0-0 | 28-42-12 | D04042J | | DED | | | TB0186Y | DED | | | 150-154, 275 |
| 18E | 24 | PV | PS | | 3-0 | 73-21-14 | D04042J | | 5 | | | TB0200F | A007 | 2 | | ALL |
| 18EZ | | | PS | | 0-0 | 73-21-14 | D04042J | | 13 | | | TB0200F | C007 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 99

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0148 | 286T0148 | | | | P6-5-L2-MN PWR DISTR PNL | | | | | | | | | | | |
| 001 | 24 | | PK | | 8-0 | 33-11-11 | D06152J | | 1 | | TB0018Y | A004 | BJ | | | ALL |
| 002 | 24 | | PK | | 8-0 | 33-16-11 | D06152J | | 6 | | TB0018Z | 12 | BJ | | | ALL |
| 003 | 24 | | PK | | 3-0 | 33-16-11 | D10272 | | X1 | | TB0018Z | 12 | BJ | | | ALL |
| 004 | 24 | | PK | | 2-0 | 33-16-11 | D10272 | | X2 | | D10274 | B1 | | | | ALL |
| 005 | 24 | | PK | | 3-0 | 33-16-11 | D10286 | | X1 | | TB0018Z | 9 | BJ | | | ALL |
| 006 | 24 | | PK | | 3-0 | 33-16-11 | D10286 | | X2 | | TB0018Z | 10 | BJ | | | ALL |
| 007 | 24 | | PK | | 7-0 | 33-16-11 | D10274 | | A1 | | D06164J | 30 | | | | ALL |
| 008 | 24 | | PK | | 4-0 | 33-16-11 | D10274 | | B2 | | TB0018X | D002 | BJ | | | ALL |
| 009 | 20 | | PA | | 3-0 | 33-16-11 | D10274 | | A2 | | GD02418 | D.. | 2 | | | ALL |
| 010 | 24 | | PK | | 3-0 | 33-16-11 | D10274 | | X1 | | TB0018Y | C006 | BJ | | | ALL |
| 011 | 24 | | PK | | 3-0 | 33-16-11 | D10274 | | X2 | | TB0018Z | 11 | BJ | | | ALL |
| 012 | 24 | | PK | | 8-0 | 33-16-11 | D06152J | | 7 | | TB0018Z | 11 | BJ | | | ALL |
| 013 | 22 | | PA | | 8-0 | 33-16-12 | D10286 | | B1 | | D06152J | 5 | | | | ALL |
| 014 | 24 | | PK | | 8-0 | 33-16-11 | D06164J | | 15 | | TB0018Z | 12 | BJ | | | ALL |
| 015 | 22 | | PA | | 6-0 | 33-16-12 | D10272 | | A3 | | C00104 | 2 | D | | | ALL |
| 016 | 22 | | PA | | 3-0 | 33-16-12 | D10272 | | A2 | | TB0018X | A002 | BJ | | | ALL |
| 017 | 22 | | PA | | 3-0 | 33-16-12 | D10272 | | A1 | | TB0018Y | A014 | BJ | | | ALL |
| 019 | 22 | | PA | | 8-0 | 33-16-12 | D06164J | | 2 | | TB0018Y | A015 | BJ | | | ALL |
| 020 | 22 | | PA | | 8-0 | 33-16-12 | D06164J | | 3 | | TB0018Y | A015 | BJ | | | ALL |
| 022 | 22 | | PA | | 8-0 | 33-16-12 | D06152J | | 2 | | TB0018Y | A015 | BJ | | | ALL |
| 023 | 22 | | PA | | 8-0 | 33-16-12 | D06164J | | 4 | | TB0018Y | A015 | BJ | | | ALL |
| 028 | 22 | | PA | | 8-0 | 33-16-12 | D06152J | | 4 | | TB0018Y | A016 | BJ | | | ALL |
| 029 | 22 | | PA | | 3-0 | 33-16-12 | D10286 | | A1 | | TB0018Y | A016 | BJ | | | ALL |
| 030 | 22 | | PA | | 8-0 | 33-16-12 | D06164J | | 6 | | TB0018Y | A016 | BJ | | | ALL |
| 031 | 22 | | PA | | 8-0 | 33-16-12 | D06164J | | 7 | | TB0018Y | A016 | BJ | | | ALL |
| 032 | 22 | | PA | | 7-0 | 33-16-12 | D06164J | | 8 | | D10286 | C1 | | | | ALL |
| 033 | 20 | | PA | | 3-0 | 33-16-12 | D10286 | | A2 | | GD02420 | D.. | 2 | | | ALL |
| 034 | 20 | | PA | | 3-0 | 33-16-12 | D10286 | | B2 | | GD02420 | D.. | 2 | | | ALL |
| 035 | 20 | | PA | | 3-0 | 33-16-12 | D10286 | | C2 | | GD02420 | D.. | 2 | | | ALL |
| 036 | 22 | | PQ | A | 6-0 | 33-16-12 | D10272 | | B3 | | C00108 | 1 | D | | | ALL |
| 036Z | | | | A | 0-0 | 33-16-12 | D10272 | | DED | | C00108 | DED | | | | ALL |
| 037 | 22 | | PA | | 3-0 | 33-16-12 | D10272 | | B2 | | TB0018X | B002 | BJ | | | ALL |
| 038 | 22 | | PA | | 3-0 | 33-16-12 | D10272 | | B1 | | TB0018Y | C016 | BJ | | | ALL |
| 039 | 22 | | PA | | 5-0 | 33-16-17 | D06164J | | 17 | | D06152J | 11 | | | | 050-099 |
| 039 | 22 | | PA | | 4-0 | 33-16-17 | D06164J | | 17 | | D06152J | 11 | | | | 150-199, 275-299 |
| 041 | 22 | | PA | | 7-0 | 33-16-17 | D06152J | | 19 | | D10286 | D1 | | | | ALL |
| 042 | 22 | | PA | | 8-0 | 33-16-17 | D06152J | | 12 | | D10286 | D2 | | | | ALL |
| 043 | 22 | | PA | | 3-0 | 33-16-21 | D10292 | | X1 | | TB0018Y | A003 | BJ | | | ALL |
| 044 | 22 | | PA | | 3-0 | 33-16-21 | D10292 | | X2 | | TB0018Y | C007 | BJ | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 100

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|---------|------|--------|------------------------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0148 | 286T0148 | | | P6-5-L2-MN PWR DISTR PNL (continued) | | | | | | | | | | | | |
| 045 | 20 | | PA | 2-0 | 33-16-21 | D10276 | A2 | | | | | GD02418 | D.. | 2 | ALL | |
| 046 | 22 | | PA | 3-0 | 33-16-21 | D10276 | X2 | | | | | TB0018Y | C008 | BJ | ALL | |
| 047 | 22 | | PA | 3-0 | 33-16-21 | D10276 | X1 | | | | | TB0018Y | A007 | BJ | ALL | |
| 048 | 22 | | PA | 7-0 | 33-16-21 | D10276 | A1 | | | | | D06164J | 20 | | ALL | |
| 049 | 22 | | PA | 6-0 | 33-16-22 | C00116 | 1 | D | | *1 | | D06164J | 10 | | ALL | |
| 050 | 22 | | PQ | 7-0 | 33-16-22 | C00116 | 2 | D | | | | D06152J | 13 | | ALL | |
| 050Z | | | | 0-0 | 33-16-22 | C00116 | | DED | | | | D06152J | DED | | ALL | |
| 051 | 22 | | PA | 7-0 | 33-16-22 | C00116 | 1 | D | | *1 | | D06152J | 14 | | ALL | |
| 052 | 22 | | PA | 8-0 | 33-16-22 | D10292 | A1 | | | | | D06152J | 15 | | ALL | |
| 053 | 22 | | PA | 8-0 | 33-16-22 | D10292 | B1 | | | | | D06152J | 16 | | ALL | |
| 054 | 22 | | PA | 8-0 | 33-16-22 | D10292 | C1 | | | | | D06152J | 17 | | ALL | |
| 055 | 20 | | PA | 3-0 | 33-16-22 | D10292 | A2 | | | | | GD02418 | D.. | 2 | ALL | |
| 056 | 20 | | PA | 3-0 | 33-16-22 | D10292 | B2 | | | | | GD02418 | D.. | 2 | ALL | |
| 057 | 20 | | PA | 3-0 | 33-16-22 | D10292 | C2 | | | | | GD02418 | D.. | 2 | ALL | |
| 058 | 24 | | PK | 8-0 | 80-11-11 | D06152J | 21 | | | | | TB0022D | A013 | 2 | ALL | |
| 059 | 24 | | PK | 2-0 | 80-11-11 | TB0022D | A001 | 2 | | | | TB0022D | A013 | 2 | ALL | |
| 060 | 24 | | PK | 4-0 | 33-16-11 | D10508 | A2 | | | | | TB0018X | B001 | BJ | ALL | |
| 061 | 24 | | PK | 4-0 | 33-16-11 | D10508 | X1 | | | | | TB0018Z | 12 | BJ | ALL | |
| 062 | 24 | | PK | 4-0 | 33-16-11 | D10508 | A1 | | | | | TB0018X | C002 | BJ | ALL | |
| 063 | 24 | | PK | 7-0 | 33-16-11 | D10508 | X2 | | | | | D06164J | 16 | | ALL | |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT | | | | | | | | | | | | |
| 001 | 16 | | PA | 3-1 | 23-12-11 | D04227P | 4 | | | | | TB0139G | 123 | 2 | 050-099, 150-157, 275-299 | |
| 001 | 16 | | PA | 3-11 | 23-12-11 | D04227P | 4 | | | | | TB0139G | 40 | 2 | 162-199 | |
| 002 | 16 | | PA | 3-3 | 23-12-21 | D04251P | 4 | | | | | TB0139G | 183 | 2 | 050-099, 150-156, 162-166, 275-276 | |
| 002 | 16 | | PA | 3-9 | 23-12-21 | D04251P | 4 | | | | | TB0139G | 171 | 2 | 157, 167-199, 277-299 | |
| 003 | 18 | | PQ | AC | 2-10 | 23-31-11 | D04227P | 7 | | | | TB0139H | 101 | 2 | 050-099, 150-199 | |
| 003 | 18 | | PQ | AC | 2-10 | 23-31-11 | D04227P | 7 | | | | TB0139G | 101 | 2 | 275-299 | |
| 003Z | | | | AC | 0-0 | 23-31-11 | D04227P | DED | | | | TB0139H | DED | | 050-099, 150-199 | |
| 003Z | | | | AC | 0-0 | 23-31-11 | D04227P | DED | | | | TB0139G | DED | | 275-299 | |
| 004 | 20 | | PQ | AD | 3-4 | 23-31-11 | D00455C | 2 | | | | TB0139H | 101 | 2 | 050-099, 150-199 | |
| 004 | 20 | | PQ | AD | 3-4 | 23-31-11 | D00455C | 2 | | | | TB0139G | 101 | 2 | 275-299 | |
| 004Z | | | | AD | 0-0 | 23-31-11 | D00455C | DED | | | | TB0139H | DED | | 050-099, 150-199 | |
| 004Z | | | | AD | 0-0 | 23-31-11 | D00455C | DED | | | | TB0139G | DED | | 275-299 | |
| 005 | 20 | | PQ | AE | 1-10 | 23-31-11 | SM00001 | | | W | | TB0139H | 101 | 2 | 050-099, 150-199 | |
| 005 | 20 | | PQ | AE | 1-10 | 23-31-11 | SM00001 | | | W | | TB0139G | 101 | 2 | 275-299 | |
| 005Z | | | | AE | 0-0 | 23-31-11 | SM00001 | DED | | | | TB0139H | DED | | 050-099, 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 101

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | | |
| 005Z | | | | AE | 0-0 | 23-31-11 | SM00001 | DED | | | | TB0139G | DED | | | 275-299 |
| 006 | 24 | PK | | | 2-6 | 23-31-11 | D00459B | D10 | | | | TB0139Z | 10 | BJ | | 050-099, 150-199 |
| 006 | 24 | PK | | | 2-6 | 23-31-11 | D00459B | D10 | | | | TB0139H | 9 | 2 | | 275-299 |
| 007 | 24 | PK | | | 3-4 | 23-31-11 | TB0139G | 109 | 2 | | | D00455B | C02 | | | 050-099 |
| 007 | 24 | PK | | | 3-0 | 23-31-11 | TB0139G | 19 | 2 | | | D00455B | C02 | | | 150-199 |
| 007 | 24 | PK | | | 3-3 | 23-31-11 | TB0139G | 40 | 2 | | | D00455B | C02 | | | 275-299 |
| 008 | 24 | PK | | | 3-0 | 23-31-11 | TB0139G | 21 | 2 | | | D00455B | D04 | | | ALL |
| 009 | 20 | PA | | | 2-2 | 23-31-11 | D00455C | 4 | | | | GD00003 | D.. | 2 | | ALL |
| 010 | 22 | PA | | | 2-0 | 23-31-11 | D00459B | D09 | | | | GD00001 | D.. | 2 | | ALL |
| 011 | 24 | PK | | | 3-11 | 23-31-12 | D04625P | 4 | | | | D00455B | D05 | | | ALL |
| 016 | 20 | PA | | | 3-2 | 23-51-11 | GDX0011 | S.. | 2 | | | D05852P | 8 | | | ALL |
| 017 | 20 | PA | | | 2-8 | 23-41-11 | GDX0001 | S.. | 2 | | | D04613P | 3 | | | ALL |
| 018 | 24 | PK | | | 4-0 | 23-31-12 | D00459B | D14 | | | | TB0139D | A140 | 2 | | 050-099, 150-199 |
| 018 | 24 | PK | | | 3-5 | 23-31-12 | D00459B | D14 | | | | D00451 | 56 | | | 275-299 |
| 019 | 24 | PK | | | 6-3 | 23-31-13 | D04963P | 3 | | | | TB0139F | A103 | 2 | | ALL |
| 01CO | | | | A | 0-0 | 23-34-14 | D00481 | = C1 | | | | D05303P | = C1 | | | ALL |
| 01CX | | BX | | A | 6-1 | 23-34-14 | D00481 | = A1 | | | | D05303P | = A1 | | | ALL |
| 020 | 24 | PK | | | 3-4 | 23-31-13 | D00455B | C09 | | | | TB0139G | 106 | 2 | | 050-099, 150-199 |
| 020 | 24 | PK | | | 3-4 | 23-31-13 | D00455B | C09 | | | | TB0139F | C103 | 2 | | 275-299 |
| 021 | 24 | PK | | | 3-4 | 23-31-13 | D00455B | D09 | | | | TB0139G | 104 | 2 | | ALL |
| 022 | 24 | PK | | | 3-4 | 23-31-13 | D00459B | B08 | | | | D00455B | A09 | | | ALL |
| 023 | 24 | PK | | | 3-4 | 23-31-13 | D00459B | B09 | | | | D00455B | B09 | | | ALL |
| 024 | 24 | PK | | | 3-4 | 23-31-13 | D00459B | C10 | | | | D00455B | B11 | | | 050-099 |
| 025 | 24 | PK | | | 3-4 | 23-31-13 | D00459B | C11 | | | | D00455B | D10 | | | ALL |
| 026 | 24 | PK | | | 3-4 | 23-31-13 | D00459B | B11 | | | | D00455B | D13 | | | ALL |
| 027 | 24 | PK | | | 3-4 | 23-31-13 | D00459B | B10 | | | | D00455B | C13 | | | ALL |
| 028 | 24 | PK | | | 3-9 | 23-32-12 | TB0139F | A144 | 2 | | | D05593P | 1 | | | ALL |
| 029 | 24 | PK | | | 5-1 | 23-32-12 | TB0139G | 104 | 2 | | | D05593P | 2 | | | ALL |
| 030 | 24 | PV | BE | | 4-7 | 23-32-12 | D00455B | A04 | | | | D05593P | 3 | | | 050-099, 150-199 |
| 030B | 24 | PW | BE | | 4-0 | 23-32-12 | D01671 | B3 | | | | D05593P | 4 | | | 275-299 |
| 030R | 24 | PW | BE | | 0-0 | 23-32-12 | D01671 | A3 | | | | D05593P | 3 | | | 275-299 |
| 030Z | | | BE | | 0-0 | 23-32-12 | D00455B | B04 | | | | D05593P | 4 | | | 050-099, 150-199 |
| 030Z | | | BE | | 0-0 | 23-32-12 | D01671 | DED | | | | D05593P | 15 | | | 275-299 |
| 031 | 24 | PK | | | 4-10 | 23-32-12 | TB0139G | 21 | 2 | | | D05593P | 5 | | | ALL |
| 032 | 24 | PV | BG | | 6-2 | 23-32-12 | D04625P | 41 | | | | D05593P | 6 | | | 050-099, 150-199 |
| 032B | 24 | PW | BG | | 6-2 | 23-32-12 | D04625P | 42 | | | | D05593P | 7 | | | 275-299 |
| 032R | 24 | PW | BG | | 0-0 | 23-32-12 | D04625P | 41 | | | | D05593P | 6 | | | 275-299 |
| 032Z | | | BG | | 0-0 | 23-32-12 | D04625P | 42 | | | | D05593P | 7 | | | 050-099, 150-199 |
| 032Z | | | BG | | 0-0 | 23-32-12 | D04625P | | | FK | | D05593P | | | FN | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 102

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | | | |
| 033 | 24 | PV | BH | 6-2 | 23-32-12 | D04625P | | 43 | | | | | D05593P | 8 | | | 050-099, 150-199 |
| 033B | 24 | PW | BH | 6-2 | 23-32-12 | D04625P | | 44 | | | | | D05593P | 9 | | | 275-299 |
| 033R | 24 | PW | BH | 0-0 | 23-32-12 | D04625P | | 43 | | | | | D05593P | 8 | | | 275-299 |
| 033Z | | | BH | 0-0 | 23-32-12 | D04625P | | 44 | | | | | D05593P | 9 | | | 050-099, 150-199 |
| 033Z | | | BH | 0-0 | 23-32-12 | D04625P | | | | | FK | | D05593P | | FN | | 275-299 |
| 034 | 24 | PV | BI | 6-2 | 23-32-12 | D04625P | | 13 | | | | | D05593P | 10 | | | 050-099, 150-199 |
| 034B | 24 | PW | BI | 6-2 | 23-32-12 | D04625P | | 14 | | | | | D05593P | 11 | | | 275-299 |
| 034R | 24 | PW | BI | 0-0 | 23-32-12 | D04625P | | 13 | | | | | D05593P | 10 | | | 275-299 |
| 034Z | | | BI | 0-0 | 23-32-12 | D04625P | | 14 | | | | | D05593P | 11 | | | 050-099, 150-199 |
| 034Z | | | BI | 0-0 | 23-32-12 | D04625P | | | | | FL | | D05593P | | FO | | 275-299 |
| 035 | 24 | PV | BJ | 6-2 | 23-32-12 | D04625P | | 17 | | | | | D05593P | 12 | | | 050-099, 150-199 |
| 035B | 24 | PW | BJ | 6-2 | 23-32-12 | D04625P | | 18 | | | | | D05593P | 13 | | | 275-299 |
| 035R | 24 | PW | BJ | 0-0 | 23-32-12 | D04625P | | 17 | | | | | D05593P | 12 | | | 275-299 |
| 035Z | | | BJ | 0-0 | 23-32-12 | D04625P | | 18 | | | | | D05593P | 13 | | | 050-099, 150-199 |
| 035Z | | | BJ | 0-0 | 23-32-12 | D04625P | | | | | FL | | D05593P | | FO | | 275-299 |
| 036 | 20 | PQ | BK | 4-7 | 23-32-11 | D04251P | | 1 | | | | | D05593P | 14 | | | ALL |
| 036Z | | | BK | 0-0 | 23-32-11 | D04251P | | | DED | | | | D05593P | | DED | | ALL |
| 037 | 24 | PK | | 0-7 | 23-41-11 | D00459A | | | C06 | | | | D00459A | C05 | | | ALL |
| 038 | 22 | PQ | BM | 3-4 | 23-34-11 | D04625P | | 11 | | | | | TB0139G | 107 | 2 | | ALL |
| 038Z | | | BM | 0-0 | 23-34-11 | D04625P | | | DED | | | | TB0139G | DED | | | ALL |
| 039 | 22 | PQ | BN | 4-6 | 23-34-11 | D04625P | | 5 | | | | | TB0139F | C145 | 2 | | ALL |
| 039Z | | | BN | 0-0 | 23-34-11 | D04625P | | | DED | | | | TB0139F | DED | | | ALL |
| 040 | 22 | PQ | BO | 3-4 | 23-34-11 | D04625P | | 45 | | | | | TB0139G | 108 | 2 | | ALL |
| 040Z | | | BO | 0-0 | 23-34-11 | D04625P | | | DED | | | | TB0139G | DED | | | ALL |
| 041 | 22 | PA | | 5-1 | 23-31-11 | D00455B | | | C11 | | | | D05678P | 4 | | | ALL |
| 042 | 22 | PA | | 5-1 | 23-31-11 | D00455B | | | D11 | | | | D05678P | 5 | | | ALL |
| 043 | 24 | PK | | 3-0 | 23-31-11 | D00455B | | | A02 | | | | TB0139G | 18 | 2 | | 050-099, 150-199 |
| 043 | 24 | PK | | 3-4 | 23-31-11 | D00455B | | | A02 | | | | D00459B | A09 | | | 275-299 |
| 044 | 22 | PA | | 2-4 | 23-31-11 | D00455B | | | B02 | | | | GDX0005 | S.. | 2 | | ALL |
| 045 | 24 | PK | | 5-3 | 23-34-13 | TB0139G | | 194 | 2 | | | | TB0139D | A019 | 2 | | 050-099 |
| 046 | 24 | PK | | 6-3 | 23-34-13 | D05421P | | 6 | | | | | TB0139G | 193 | 2 | | 050-099 |
| 047 | 24 | PK | | 2-6 | 23-31-11 | D00459B | | | A07 | | | | TB0139Z | 9 | BJ | | 050-099, 150-199 |
| 047 | 24 | PK | | 2-6 | 23-31-11 | D00459B | | | A07 | | | | TB0139H | 7 | 2 | | 275-299 |
| 051 | 24 | PK | | 3-3 | 23-12-21 | D04963P | | 11 | | | | | TB0139G | 184 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 051 | 24 | PK | | 3-3 | 23-12-21 | D04963P | | 11 | | | | | TB0139Y | C184 | BJ | | 157, 167-199, 277-299 |
| 055 | 24 | PK | | 3-8 | 23-34-13 | D04625P | | 25 | | | | | TB0139G | 122 | 2 | | 050-099 |
| 056 | 24 | PK | | 2-11 | 23-34-13 | D00455B | | | A11 | | | | TB0139G | 122 | 2 | | 050-099 |
| 057 | 22 | PQ | CG | 3-6 | 23-42-12 | TB0139G | | 122 | 2 | | | | D04647P | 10 | | | 150-157, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 103

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | |
| 057 | 22 | PQ | | CG | 3-6 | 23-42-12 | TB0139Z | 122 | BJ | | D04647P | 10 | | | 162-199 |
| 057Z | | | | CG | 0-0 | 23-42-12 | TB0139G | DED | | | D04647P | DED | | | 150-157, 275-299 |
| 057Z | | | | CG | 0-0 | 23-42-12 | TB0139Z | DED | | | D04647P | DED | | | 162-199 |
| 058 | 24 | PK | | | 3-2 | 23-42-12 | D00459A | C01 | | | D04647P | 11 | | | 150-199, 275-299 |
| 059 | 24 | PK | | | 3-2 | 23-42-12 | D00459A | C02 | | | D04647P | 12 | | | 150-199, 275-299 |
| 060 | 24 | PK | | | 3-2 | 23-42-12 | D00459A | C03 | | | D04647P | 13 | | | 150-199, 275-299 |
| 071 | 22 | PA | | | 3-1 | 23-42-11 | D00459B | C01 | | | TB0139F | C120 | 2 | | ALL |
| 072 | 24 | PK | | | 4-4 | 31-51-33 | D00459A | A13 | | | TB0139D | A157 | 2 | | 050-099, 162-199 |
| 072 | 24 | PK | | | 4-0 | 31-51-33 | D00459A | A13 | | | TB0139F | C141 | 2 | | 150-157, 275-299 |
| 076 | 24 | PK | | | 3-1 | 23-11-21 | D05719J | 11 | | | TB0139G | 182 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 076 | 24 | PK | | | 3-1 | 23-11-21 | D05719J | 11 | | | TB0139Y | A184 | BJ | | 157, 167-199, 277-299 |
| 077 | 22 | PQ | DB | | 4-4 | 23-34-12 | D00449 | 4 | | | D04625P | 12 | | | 050-099 |
| 077 | 24 | PV | DB | | 4-4 | 23-34-12 | D00449 | 4 | | | D04625P | 12 | | | 150-199, 275-299 |
| 077Z | | | DB | | 0-0 | 23-34-12 | D00449 | DED | | | D04625P | DED | | | ALL |
| 082 | 20 | PA | | | 1-11 | 23-34-11 | D00449 | 2 | | | GDX0007 | S.. | 2 | | ALL |
| 083 | 20 | PA | | | 1-11 | 23-34-11 | D00449 | 7 | | | GDX0007 | D.. | 2 | | ALL |
| 084 | 20 | PA | | | 1-11 | 23-34-11 | D00451 | 16 | | | GDX0007 | S.. | 2 | | ALL |
| 087 | 22 | PQ | DL | | 2-5 | 23-42-11 | D00459A | D01 | | | TB0139H | 111 | 2 | | 050-099 |
| 087 | 22 | PQ | DL | | 3-1 | 23-42-11 | D00459A | D01 | | | TB0139G | 122 | 2 | | 150-157, 275-299 |
| 087 | 22 | PQ | DL | | 3-1 | 23-42-11 | D00459A | D01 | | | TB0139Z | 122 | BJ | | 162-199 |
| 087Z | | | DL | | 0-0 | 23-42-11 | D00459A | DED | | | TB0139H | DED | | | 050-099 |
| 087Z | | | DL | | 0-0 | 23-42-11 | D00459A | DED | | | TB0139G | DED | | | 150-157, 275-299 |
| 087Z | | | DL | | 0-0 | 23-42-11 | D00459A | DED | | | TB0139Z | DED | | | 162-199 |
| 088 | 22 | PA | | | 2-0 | 23-42-11 | D00459A | D02 | | | GDX0001 | D.. | 2 | | ALL |
| 089 | 22 | PA | | | 3-9 | 23-42-11 | D00459A | C08 | | | TB0139F | A135 | 2 | | ALL |
| 090 | 22 | PA | | | 3-9 | 23-42-11 | D00459A | C09 | | | TB0139F | C135 | 2 | | ALL |
| 091 | 22 | PA | | | 3-9 | 23-42-11 | D00459A | C10 | | | TB0139F | A136 | 2 | | ALL |
| 092 | 22 | PA | | | 3-9 | 23-42-11 | D00459A | C11 | | | TB0139F | C136 | 2 | | ALL |
| 093 | 22 | PQ | DR | | 3-9 | 23-42-11 | D00459A | B12 | | | TB0139F | A137 | 2 | | ALL |
| 093Z | | | DR | | 0-0 | 23-42-11 | D00459A | B13 | | | TB0139F | C137 | 2 | | ALL |
| 100 | 22 | PA | | | 4-0 | 23-42-11 | D00459B | D13 | | | TB0139F | C140 | 2 | | 280-299 |
| 102 | 20 | PA | | | 2-0 | 23-42-11 | D00459C | 2 | | | GDX0001 | S.. | 2 | | ALL |
| 103 | 22 | PA | | | 3-2 | 23-42-11 | D00459A | C13 | | | D04647P | 5 | | | ALL |
| 104 | 22 | PQ | ED | | 2-10 | 23-42-11 | D04227P | 1 | | | TB0139H | 111 | 2 | | 050-099 |
| 104 | 22 | PQ | ED | | 3-1 | 23-42-11 | D04227P | 1 | | | TB0139G | 122 | 2 | | 150-157, 275-299 |
| 104 | 22 | PQ | ED | | 3-1 | 23-42-11 | D04227P | 1 | | | TB0139Z | 122 | BJ | | 162-199 |
| 104Z | | | ED | | 0-0 | 23-42-11 | D04227P | DED | | | TB0139H | DED | | | 050-099 |
| 104Z | | | ED | | 0-0 | 23-42-11 | D04227P | DED | | | TB0139G | DED | | | 150-157, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 104

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | | | |
| 104Z | | | | ED | 0-0 | 23-42-11 | D04227P | DED | | | | | TB0139Z | DED | | | 162-199 |
| 105 | 22 | PA | | | 3-2 | 23-42-11 | D00459A | C14 | | | | | D04647P | 3 | | | ALL |
| 106 | 20 | PA | | | 2-6 | 23-43-11 | TB0139D | A124 | 2 | | | | GDX0005 | D.. | 2 | | ALL |
| 108 | 22 | PA | | | 3-2 | 23-42-11 | D00459A | C12 | | | | | D04647P | 4 | | | ALL |
| 109 | 20 | PA | | | 3-7 | 23-43-11 | TB0139D | A124 | 2 | | | | D04613P | 8 | | | ALL |
| 110 | 22 | PA | | | 6-0 | 23-43-11 | D05852P | | 1 | | | | TB0139F | A119 | 2 | | ALL |
| 111 | 22 | PA | | | 6-0 | 23-43-11 | D05852P | | 2 | | | | TB0139F | C119 | 2 | | ALL |
| 112 | 22 | PA | | | 3-7 | 23-43-11 | D04613P | | 7 | | | | TB0139D | C124 | 2 | | ALL |
| 113 | 22 | PA | | | 2-10 | 23-51-11 | D00459B | A01 | | | | | D04227P | 2 | | | ALL |
| 114 | 22 | PA | | | 2-0 | 23-51-11 | D00459B | A02 | | | | | GDX0001 | D.. | 2 | | ALL |
| 115 | 22 | PA | | | 2-0 | 23-51-11 | D00459B | C02 | | | | | GDX0001 | S.. | 2 | | ALL |
| 116 | 22 | PA | | | 2-0 | 23-51-11 | D00459A | B01 | | | | | GDX0001 | S.. | 2 | | ALL |
| 122 | 24 | PK | | | 2-6 | 23-51-41 | D00459B | B06 | | | | | TB0139F | A013 | 2 | | ALL |
| 124 | 24 | PK | | | 5-3 | 33-25-11 | D05678P | | 3 | | | | TB0139G | 122 | 2 | | 050-099 |
| 125 | 22 | PA | | | 4-5 | 23-71-11 | D04251P | | 2 | | | | TB0139F | A141 | 2 | | ALL |
| 126 | 24 | PK | | | 0-7 | 23-31-13 | D00455B | B10 | | | | | D00455B | C10 | | | 050-099 |
| 129 | 24 | PK | | | 3-2 | 23-31-11 | D00459B | D12 | | | | | TB0139G | 21 | 2 | | 275-299 |
| 134 | 22 | PA | | | 0-6 | 23-31-11 | D00459B | D08 | | | | | SM00001 | | W | | ALL |
| 135 | 24 | PK | | | 2-2 | 23-11-21 | D05719J | | 10 | | | | TB0139H | 57 | 2 | | ALL |
| 141 | 20 | PQ | FP | | 3-3 | 23-31-12 | D01671 | X1 | | | | | TB0139G | 101 | 2 | | 275-299 |
| 141Z | | | FP | | 0-0 | 23-31-12 | D01671 | DED | | | | | TB0139G | DED | | | 275-299 |
| 142 | 24 | PK | | | 3-3 | 23-31-12 | D01671 | X2 | | | | | TB0139D | C150 | 2 | | 275-299 |
| 143 | 24 | PK | | | 4-10 | 23-31-12 | D04625P | | 48 | | | | TB0139D | C150 | 2 | | 275-299 |
| 144 | 24 | PK | | | 4-0 | 23-31-12 | TB0139G | | 21 | 2 | | | TB0139D | A150 | 2 | | 275-299 |
| 145 | 24 | PK | | | 3-4 | 23-31-12 | D04625P | | 29 | | | | TB0139G | 104 | 2 | | 275-299 |
| 147 | 24 | PV | FV | | 2-8 | 23-31-12 | D00455B | A04 | | | | | D01671 | A2 | | | 275-299 |
| 147Z | | | FV | | 0-0 | 23-31-12 | D00455B | B04 | | | | | D01671 | B2 | | | 275-299 |
| 152 | 24 | PV | GB | | 5-4 | 23-32-12 | D05421P | | 1 | | | | D05593P | 20 | | | 050-099, 150-199 |
| 152B | 24 | PW | GB | | 5-4 | 23-32-12 | D05421P | | 2 | | | | D05593P | 21 | | | 275-299 |
| 152R | 24 | PW | GB | | 0-0 | 23-32-12 | D05421P | | 1 | | | | D05593P | 20 | | | 275-299 |
| 152Z | | | GB | | 0-0 | 23-32-12 | D05421P | | 2 | | | | D05593P | 21 | | | 050-099, 150-199 |
| 152Z | | | GB | | 0-0 | 23-32-12 | D05421P | | | | FM | | D05593P | | | FP | 275-299 |
| 153 | 24 | PV | GC | | 5-4 | 23-32-12 | D05421P | | 3 | | | | D05593P | 22 | | | 050-099, 150-199 |
| 153B | 24 | PW | GC | | 5-4 | 23-32-12 | D05421P | | 4 | | | | D05593P | 23 | | | 275-299 |
| 153R | 24 | PW | GC | | 0-0 | 23-32-12 | D05421P | | 3 | | | | D05593P | 22 | | | 275-299 |
| 153Z | | | GC | | 0-0 | 23-32-12 | D05421P | | 4 | | | | D05593P | 23 | | | 050-099, 150-199 |
| 153Z | | | GC | | 0-0 | 23-32-12 | D05421P | | | | FM | | D05593P | | | FP | 275-299 |
| 154 | 24 | PK | | | 3-7 | 23-34-13 | TB0139D | C019 | 2 | | | | D04647P | 14 | | | 050-099 |
| 155 | 24 | PK | | | 2-10 | 23-34-13 | TB0139D | C019 | 2 | | | | TB0139D | C020 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 105

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | |
| 156 | 24 | | PK | 6-5 | 23-34-13 | TB0139G | 193 | 2 | | D04647P | 9 | | | 050-099 | |
| 157 | 24 | | PK | 5-3 | 23-34-13 | TB0139G | 193 | 2 | | TB0139D | A020 | 2 | | 050-099 | |
| 177 | 24 | | PK | 3-10 | 23-31-11 | D00459B | | D11 | | TB0139G | 40 | 2 | | 275-299 | |
| 178 | 24 | | PK | 4-5 | 23-31-12 | D04625P | | 3 | | TB0139G | 40 | 2 | | 275-299 | |
| 179 | 24 | | PK | 3-5 | 23-31-12 | D04625P | | 49 | | TB0139H | 9 | 2 | | 275-299 | |
| 195 | 22 | | PA | 6-2 | 23-24-11 | TB0139F | | A196 | 2 | D04629P | 12 | | | 050-099 | |
| 195 | 22 | | PA | 6-2 | 23-24-11 | TB0139X | | A196 | BJ | D04629P | 12 | | | 150-199 | |
| 196 | 22 | | PA | 6-2 | 23-24-11 | TB0139F | | C196 | 2 | D04629P | 13 | | | 050-099 | |
| 196 | 22 | | PA | 6-2 | 23-24-11 | TB0139X | | B196 | BJ | D04629P | 13 | | | 150-199 | |
| 197 | 20 | | PQ | 3-2 | 23-31-11 | D02267 | | 25 | | TB0139H | 101 | 2 | | 050-099, 150-199 | |
| 197Z | | | | 0-0 | 23-31-11 | D02267 | | DED | | TB0139H | DED | | | 050-099, 150-199 | |
| 199 | 20 | | PQ | 3-10 | 23-31-13 | TB0139G | | 34 | 2 | TB0139H | 101 | 2 | | 050-099, 150-199 | |
| 199Z | | | | 0-0 | 23-31-13 | TB0139G | | DED | | TB0139H | DED | | | 050-099, 150-199 | |
| 201B | 24 | | PL | 3-1 | 23-21-11 | D05719J | | 2 | | TB0139F | C185 | 2 | | 050-099, 150-156, 162-166, 275-276 | |
| 201B | 24 | | PL | 3-1 | 23-21-11 | D05719J | | 2 | | TB0139Y | C185 | BJ | | 157, 167-199, 277-299 | |
| 201R | 24 | | PL | 0-0 | 23-21-11 | D05719J | | 1 | | TB0139F | A185 | 2 | | 050-099, 150-156, 162-166, 275-276 | |
| 201R | 24 | | PL | 0-0 | 23-21-11 | D05719J | | 1 | | TB0139Y | A185 | BJ | | 157, 167-199, 277-299 | |
| 205B | 24 | | PL | 6-4 | 23-51-11 | D00459B | | A06 | | D05852P | 6 | | | ALL | |
| 205R | 24 | | PL | 0-0 | 23-51-11 | D00459B | | B07 | | D05852P | 7 | | | ALL | |
| 206B | 24 | | PL | 3-3 | 23-41-11 | D00459A | | C04 | | D04613P | 2 | | | ALL | |
| 206R | 24 | | PL | 0-0 | 23-41-11 | D00459A | | C07 | | D04613P | 1 | | | ALL | |
| 207B | 24 | | PL | 3-10 | 23-31-13 | D00459B | | A14 | | TB0139G | 31 | 2 | | 050-099, 150-199 | |
| 207B | 24 | | PL | 3-4 | 23-31-13 | D00459B | | A14 | | D04625P | 16 | | | 275-299 | |
| 207R | 24 | | PL | 0-0 | 23-31-13 | D00459B | | A15 | | TB0139G | 30 | 2 | | 050-099, 150-199 | |
| 207R | 24 | | PL | 0-0 | 23-31-13 | D00459B | | A15 | | D04625P | 15 | | | 275-299 | |
| 208B | 22 | | PB | 3-9 | 23-31-14 | D04647P | | 2 | | D00455B | B13 | | | 050-099 | |
| 208R | 22 | | PB | 0-0 | 23-31-14 | D04647P | | 1 | | D00455B | A13 | | | 050-099 | |
| 209B | 22 | | PB | 5-3 | 23-31-14 | D05678P | | 2 | | TB0139G | 128 | 2 | | 050-099, 150-199 | |
| 209B | 22 | | PB | 5-3 | 23-31-14 | D05678P | | 2 | | TB0139G | 118 | 2 | | 275-299 | |
| 209R | 22 | | PB | 0-0 | 23-31-14 | D05678P | | 1 | | TB0139G | 127 | 2 | | 050-099, 150-199 | |
| 209R | 22 | | PB | 0-0 | 23-31-14 | D05678P | | 1 | | TB0139G | 117 | 2 | | 275-299 | |
| 216B | 24 | | PL | 2-5 | 23-41-11 | D00459A | | B09 | | TB0139F | C105 | 2 | | ALL | |
| 216R | 24 | | PL | 0-0 | 23-41-11 | D00459A | | B08 | | TB0139F | A105 | 2 | | ALL | |
| 224B | 24 | | PL | 2-4 | 23-34-14 | D00449 | | 19 | | D00451 | 54 | | | ALL | |
| 224R | 24 | | PL | 0-0 | 23-34-14 | D00449 | | 11 | | D00451 | 53 | | | ALL | |
| 225B | 24 | | PL | 2-4 | 23-34-14 | D00449 | | 22 | | D00451 | 63 | | | ALL | |
| 225R | 24 | | PL | 0-0 | 23-34-14 | D00449 | | 14 | | D00451 | 62 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 106

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | |
| 226B | 24 | PL | JA | | 2-4 | 23-34-14 | D00449 | | 21 | | D00451 | 65 | | | ALL |
| 226R | 24 | PL | JA | | 0-0 | 23-34-14 | D00449 | | 13 | | D00451 | 64 | | | ALL |
| 227B | 24 | PL | JB | | 2-4 | 23-34-14 | D00449 | | 20 | | D00451 | 61 | | | ALL |
| 227R | 24 | PL | JB | | 0-0 | 23-34-14 | D00449 | | 12 | | D00451 | 60 | | | ALL |
| 228B | 24 | PL | JC | | 2-4 | 23-34-14 | D00449 | | 23 | | D00451 | 67 | | | ALL |
| 228R | 24 | PL | JC | | 0-0 | 23-34-14 | D00449 | | 15 | | D00451 | 66 | | | ALL |
| 229B | 24 | PL | JD | | 2-4 | 23-34-14 | D00449 | | 32 | | D00451 | 52 | | | ALL |
| 229R | 24 | PL | JD | | 0-0 | 23-34-14 | D00449 | | 31 | | D00451 | 51 | | | ALL |
| 230B | 24 | PL | JE | | 2-4 | 23-34-14 | D00449 | | 18 | | D00451 | 50 | | | ALL |
| 230R | 24 | PL | JE | | 0-0 | 23-34-14 | D00449 | | 10 | | D00451 | 49 | | | ALL |
| 231B | 24 | PL | JF | | 2-4 | 23-34-14 | D00449 | | 30 | | D00451 | 48 | | | ALL |
| 231R | 24 | PL | JF | | 0-0 | 23-34-14 | D00449 | | 29 | | D00451 | 47 | | | ALL |
| 232B | 24 | PL | JG | | 2-4 | 23-34-14 | D00449 | | 28 | | D00451 | 29 | | | ALL |
| 232R | 24 | PL | JG | | 0-0 | 23-34-14 | D00449 | | 27 | | D00451 | 28 | | | ALL |
| 233B | 24 | PL | JH | | 2-4 | 23-34-14 | D00449 | | 26 | | D00451 | 25 | | | ALL |
| 233R | 24 | PL | JH | | 0-0 | 23-34-14 | D00449 | | 25 | | D00451 | 24 | | | ALL |
| 234 | 20 | UA | | | 3-3 | 23-31-12 | GDX0003 | | S.. | 2 | D04625P | | | FH | 150-199, 275-299 |
| 234B | 24 | PW | JI | | 2-10 | 23-31-12 | D00455B | | B05 | | D00451 | 42 | | | 050-099 |
| 234B | 24 | PW | JI | | 3-11 | 23-31-12 | D00455B | | B05 | | D04625P | 8 | | | 150-199 |
| 234B | 24 | PW | JI | | 3-11 | 23-31-12 | D00455B | | B05 | | D04625P | 50 | | | 275-299 |
| 234R | 24 | PW | JI | | 0-0 | 23-31-12 | D00455B | | A05 | | D00451 | 41 | | | 050-099 |
| 234R | 24 | PW | JI | | 0-0 | 23-31-12 | D00455B | | A05 | | D04625P | 9 | | | 150-199 |
| 234R | 24 | PW | JI | | 0-0 | 23-31-12 | D00455B | | A05 | | D04625P | 2 | | | 275-299 |
| 234Z | | | JI | | 0-0 | 23-31-12 | GDX0003 | | S.. | 2 | D00451 | DED | | | 050-099 |
| 234Z | | | JI | | 0-0 | 23-31-12 | D00455B | | DED | | D04625P | | | FH | 150-199, 275-299 |
| 236B | 24 | PL | JK | | 2-6 | 23-51-11 | D00459B | | A04 | | TB0139G | 4 | 2 | | ALL |
| 236R | 24 | PL | JK | | 0-0 | 23-51-11 | D00459B | | B03 | | TB0139F | C003 | 2 | | ALL |
| 237B | 24 | PL | JL | | 3-6 | 23-51-11 | D00455B | | B14 | | GDY0001 | S.. | 2 | | ALL |
| 237R | 24 | PL | JL | | 0-0 | 23-51-11 | D00455B | | A14 | | TB0139Z | 11 | BJ | | 050-099, 150-199 |
| 237R | 24 | PL | JL | | 0-0 | 23-51-11 | D00455B | | A14 | | TB0139H | 11 | 2 | | 275-299 |
| 238B | 24 | PL | JM | | 4-0 | 23-34-14 | D04625P | | 20 | | D00451 | 23 | | | ALL |
| 238R | 24 | PL | JM | | 0-0 | 23-34-14 | D04625P | | 19 | | D00451 | 22 | | | ALL |
| 239B | 24 | PL | JN | | 4-0 | 23-34-14 | D04625P | | 22 | | D00451 | 27 | | | ALL |
| 239R | 24 | PL | JN | | 0-0 | 23-34-14 | D04625P | | 21 | | D00451 | 26 | | | ALL |
| 240 | 20 | UA | | | 3-3 | 23-31-12 | GDX0003 | | S.. | 2 | D04625P | | | FI | 275-299 |
| 240B | 24 | PW | JO | | 3-9 | 23-31-12 | D01671 | | B1 | | D04625P | 46 | | | 275-299 |
| 240R | 24 | PW | JO | | 0-0 | 23-31-12 | D01671 | | A1 | | D04625P | 47 | | | 275-299 |
| 240Z | | | JO | | 0-0 | 23-31-12 | D01671 | | DED | | D04625P | | | FI | 275-299 |
| 241B | 24 | PL | JP | | 3-8 | 23-51-13 | D04581P | | 2 | | GDY0009 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 107

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | |
| 241R | 24 | PL | JP | | 0-0 | 23-51-13 | D04581P | | | | TB0139H | 53 | 2 | | ALL |
| 242B | 24 | PL | JQ | | 2-4 | 23-51-14 | D05719J | | | | GDY0009 | S.. | 2 | | ALL |
| 242R | 24 | PL | JQ | | 0-0 | 23-51-14 | D05719J | | | | TB0139H | 59 | 2 | | ALL |
| 243B | 24 | PL | JR | | 2-6 | 23-51-21 | D00459B | | A05 | | TB0139G | 14 | 2 | | ALL |
| 243R | 24 | PL | JR | | 0-0 | 23-51-21 | D00459B | | B04 | | TB0139F | C013 | 2 | | ALL |
| 244B | 22 | PB | JS | | 3-1 | 23-31-14 | D00459B | | B14 | | TB0139Z | 118 | BJ | | 050-099, 150-199 |
| 244B | 22 | PB | JS | | 3-1 | 23-31-14 | D00459B | | B14 | | TB0139G | 118 | 2 | | 275-299 |
| 244R | 22 | PB | JS | | 0-0 | 23-31-14 | D00459B | | B15 | | TB0139Z | 117 | BJ | | 050-099, 150-199 |
| 244R | 22 | PB | JS | | 0-0 | 23-31-14 | D00459B | | B15 | | TB0139G | 117 | 2 | | 275-299 |
| 245B | 22 | PB | JT | | 2-11 | 23-31-14 | D00455B | | B15 | | TB0139Z | 118 | BJ | | 050-099, 150-199 |
| 245B | 22 | PB | JT | | 2-11 | 23-31-14 | D00455B | | B15 | | TB0139G | 118 | 2 | | 275-299 |
| 245R | 22 | PB | JT | | 0-0 | 23-31-14 | D00455B | | A15 | | TB0139Z | 117 | BJ | | 050-099, 150-199 |
| 245R | 22 | PB | JT | | 0-0 | 23-31-14 | D00455B | | A15 | | TB0139G | 117 | 2 | | 275-299 |
| 246B | 24 | PL | JU | | 3-2 | 23-41-11 | D00459A | | B11 | | TB0139G | 23 | 2 | | ALL |
| 246R | 24 | PL | JU | | 0-0 | 23-41-11 | D00459A | | B10 | | TB0139G | 22 | 2 | | ALL |
| 247B | 22 | PB | JV | | 4-3 | 23-34-11 | D00451 | | 10 | | D04963P | 6 | | | ALL |
| 247R | 22 | PB | JV | | 0-0 | 23-34-11 | D00451 | | 1 | | D04963P | 5 | | | ALL |
| 248B | 22 | PB | JW | | 4-4 | 23-34-11 | D00449 | | 3 | | D04625P | 28 | | | ALL |
| 248R | 22 | PB | JW | | 0-0 | 23-34-11 | D00449 | | 1 | | D04625P | 23 | | | ALL |
| 253B | 24 | PW | KC | | 3-1 | 31-35-13 | D04581P | | 7 | | TB0139F | C035 | 2 | | 050-099, 150-199 |
| 253B | 24 | PW | KC | | 3-1 | 31-35-13 | D04581P | | 7 | | TB0139F | C033 | 2 | | 275-299 |
| 253R | 24 | PW | KC | | 0-0 | 31-35-13 | D04581P | | 6 | | TB0139F | A035 | 2 | | 050-099, 150-199 |
| 253R | 24 | PW | KC | | 0-0 | 31-35-13 | D04581P | | 6 | | TB0139F | A033 | 2 | | 275-299 |
| 253Z | | | KC | | 0-0 | 31-35-13 | D04581P | | 8 | | GDY0007 | S.. | 2 | | ALL |
| 254B | 24 | PL | KD | | 3-10 | 23-31-13 | D02271 | | 32 | | TB0139G | 31 | 2 | | 050-099, 150-199 |
| 254R | 24 | PL | KD | | 0-0 | 23-31-13 | D02271 | | 38 | | TB0139G | 30 | 2 | | 050-099, 150-199 |
| 255B | 24 | PL | KE | | 3-10 | 23-31-13 | D02271 | | 28 | | TB0139G | 31 | 2 | | 050-099, 150-199 |
| 255R | 24 | PL | KE | | 0-0 | 23-31-13 | D02271 | | 43 | | TB0139G | 30 | 2 | | 050-099, 150-199 |
| 256B | 24 | PL | KF | | 3-10 | 23-31-13 | D02271 | | 26 | | TB0139G | 31 | 2 | | 050-099, 150-199 |
| 256R | 24 | PL | KF | | 0-0 | 23-31-13 | D02271 | | 14 | | TB0139G | 30 | 2 | | 050-099, 150-199 |
| 257B | 22 | PB | KG | | 3-1 | 23-31-14 | D02267 | | 42 | | TB0139Z | 118 | BJ | | 050-099, 150-199 |
| 257R | 22 | PB | KG | | 0-0 | 23-31-14 | D02267 | | 43 | | TB0139Z | 117 | BJ | | 050-099, 150-199 |
| 260B | 24 | PL | KJ | | 3-11 | 23-51-13 | D04581P | | 5 | | GDY0003 | S.. | 2 | | ALL |
| 260R | 24 | PL | KJ | | 0-0 | 23-51-13 | D04581P | | 4 | | TB0139Z | 26 | 2 | | 050-099 |
| 260R | 24 | PL | KJ | | 0-0 | 23-51-13 | D04581P | | 4 | | TB0139Z | 26 | BJ | | 150-199 |
| 260R | 24 | PL | KJ | | 0-0 | 23-51-13 | D04581P | | 4 | | TB0139H | 26 | 2 | | 275-299 |
| 265B | 22 | PB | KO | | 3-2 | 23-31-14 | TB0139Z | | 118 | BJ | TB0139G | 126 | 2 | | 050-099, 150-199 |
| 265R | 22 | PB | KO | | 0-0 | 23-31-14 | TB0139Z | | 117 | BJ | TB0139G | 125 | 2 | | 050-099, 150-199 |
| 266B | 22 | PB | KP | | 3-1 | 23-31-14 | D02269 | | 39 | | TB0139G | 126 | 2 | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 108

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | |
| 266R | 22 | PB | KP | | 0-0 | 23-31-14 | D02269 | | 41 | | TB0139G | 125 | 2 | | 050-099, 150-199 |
| 267B | 22 | PB | KQ | | 3-1 | 23-31-14 | D02269 | | 27 | | TB0139G | 126 | 2 | | 050-099, 150-199 |
| 267R | 22 | PB | KQ | | 0-0 | 23-31-14 | D02269 | | 42 | | TB0139G | 125 | 2 | | 050-099, 150-199 |
| 268B | 22 | PB | KR | | 3-1 | 23-31-14 | D02269 | | 10 | | TB0139G | 126 | 2 | | 050-099, 150-199 |
| 268R | 22 | PB | KR | | 0-0 | 23-31-14 | D02269 | | 18 | | TB0139G | 125 | 2 | | 050-099, 150-199 |
| 269B | 22 | PB | KS | | 3-1 | 23-31-14 | D02269 | | 21 | | TB0139G | 128 | 2 | | 050-099, 150-199 |
| 269R | 22 | PB | KS | | 0-0 | 23-31-14 | D02269 | | 2 | | TB0139G | 127 | 2 | | 050-099, 150-199 |
| 271B | 24 | PW | KU | | 4-2 | 23-22-12 | D05421P | | 25 | | TB0139F | C149 | 2 | | 050-099, 150-199, 275-278 |
| 271R | 24 | PW | KU | | 0-0 | 23-22-12 | D05421P | | 24 | | TB0139F | A149 | 2 | | 050-099, 150-199, 275-278 |
| 271Z | | | KU | | 0-0 | 23-22-12 | D05421P | | 26 | | TB0139F | A151 | 2 | | 050-099, 150-199, 275-278 |
| 272B | 24 | PW | KV | | 4-6 | 23-22-12 | D05421P | | 28 | | TB0139F | C150 | 2 | | 050-099, 150-199 |
| 272B | 24 | PW | KV | | 4-6 | 23-22-12 | D05421P | | 28 | | TB0139F | C157 | 2 | | 275-278 |
| 272R | 24 | PW | KV | | 0-0 | 23-22-12 | D05421P | | 27 | | TB0139F | A150 | 2 | | 050-099, 150-199 |
| 272R | 24 | PW | KV | | 0-0 | 23-22-12 | D05421P | | 27 | | TB0139F | A157 | 2 | | 275-278 |
| 272Z | | | KV | | 0-0 | 23-22-12 | D05421P | | 29 | | TB0139F | C151 | 2 | | 050-099, 150-199 |
| 272Z | | | KV | | 0-0 | 23-22-12 | D05421P | | 29 | | TB0139F | C156 | 2 | | 275-278 |
| 273B | 22 | PB | KW | | 4-2 | 23-22-12 | D05421P | | 31 | | TB0139G | 148 | 2 | | 050-099, 150-199, 275-278 |
| 273R | 22 | PB | KW | | 0-0 | 23-22-12 | D05421P | | 30 | | TB0139G | CAP | Y | | 050-099, 150-199, 275-278 |
| 274B | 22 | PB | KX | | 3-1 | 23-31-14 | D02269 | | 32 | | TB0139G | 128 | 2 | | 050-099, 150-199 |
| 274R | 22 | PB | KX | | 0-0 | 23-31-14 | D02269 | | 38 | | TB0139G | 127 | 2 | | 050-099, 150-199 |
| 275B | 22 | PB | KY | | 6-2 | 23-31-14 | D02269 | | 28 | | D05678P | 9 | | | 050-099, 150-199 |
| 275R | 22 | PB | KY | | 0-0 | 23-31-14 | D02269 | | 43 | | D05678P | 8 | | | 050-099, 150-199 |
| 276B | 22 | PB | LA | | 6-2 | 23-31-14 | D02269 | | 26 | | D05678P | 7 | | | 050-099, 150-199 |
| 276R | 22 | PB | LA | | 0-0 | 23-31-14 | D02269 | | 14 | | D05678P | 6 | | | 050-099, 150-199 |
| 277B | 22 | PB | LB | | 6-2 | 23-31-14 | D02269 | | 15 | | D05678P | 11 | | | 050-099, 150-199 |
| 277R | 22 | PB | LB | | 0-0 | 23-31-14 | D02269 | | 1 | | D05678P | 10 | | | 050-099, 150-199 |
| 278B | 24 | PL | LC | | 3-1 | 23-31-13 | D02271 | | 40 | | TB0139Z | 118 | BJ | | 050-099, 150-199 |
| 278R | 24 | PL | LC | | 0-0 | 23-31-13 | D02271 | | 36 | | TB0139Z | 117 | BJ | | 050-099, 150-199 |
| 279B | 24 | PL | LD | | 3-1 | 23-31-13 | D02271 | | 44 | | TB0139Z | 118 | BJ | | 050-099, 150-199 |
| 279R | 24 | PL | LD | | 0-0 | 23-31-13 | D02271 | | 35 | | TB0139Z | 117 | BJ | | 050-099, 150-199 |
| 280B | 24 | PL | LE | | 3-1 | 23-31-13 | D02271 | | 22 | | TB0139Z | 118 | BJ | | 050-099, 150-199 |
| 280R | 24 | PL | LE | | 0-0 | 23-31-13 | D02271 | | 12 | | TB0139Z | 117 | BJ | | 050-099, 150-199 |
| 281B | 24 | PL | LF | | 3-8 | 23-31-13 | D02271 | | 39 | | D04625P | 47 | | | 050-099, 150-199 |
| 281R | 24 | PL | LF | | 0-0 | 23-31-13 | D02271 | | 41 | | D04625P | 46 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 109

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | |
| 282B | 24 | PL | LG | | 3-8 | 23-31-13 | D02271 | | 27 | | D04625P | | 49 | | 050-099, 150-199 |
| 282R | 24 | PL | LG | | 0-0 | 23-31-13 | D02271 | | 42 | | D04625P | | 48 | | 050-099, 150-199 |
| 283B | 24 | PL | LH | | 3-8 | 23-31-13 | D02271 | | 10 | | D04625P | | 51 | | 050-099, 150-199 |
| 283R | 24 | PL | LH | | 0-0 | 23-31-13 | D02271 | | 18 | | D04625P | | 50 | | 050-099, 150-199 |
| 302B | 24 | PM | MB | | 3-9 | 23-41-11 | D04613P | | 5 | | TB0139G | | 23 | 2 | ALL |
| 302R | 24 | PM | MB | | 0-0 | 23-41-11 | D04613P | | 4 | | TB0139G | | 22 | 2 | ALL |
| 302Y | 24 | PM | MB | | 0-0 | 23-41-11 | D04613P | | 6 | | GDY0003 | S.. | 2 | | ALL |
| 303B | 24 | PM | MC | | 3-6 | 23-51-11 | D00455B | B01 | | | GDY0001 | S.. | 2 | | ALL |
| 303R | 24 | PM | MC | | 0-0 | 23-51-11 | D00455B | A01 | | | TB0139Z | 9 | BJ | | 050-099, 150-199 |
| 303R | 24 | PM | MC | | 0-0 | 23-51-11 | D00455B | A01 | | | TB0139H | 7 | 2 | | 275-299 |
| 303Y | 24 | PM | MC | | 0-0 | 23-51-11 | D00455B | C01 | | | TB0139Z | 10 | BJ | | 050-099, 150-199 |
| 303Y | 24 | PM | MC | | 0-0 | 23-51-11 | D00455B | C01 | | | TB0139H | 9 | 2 | | 275-299 |
| 305B | 24 | PM | ME | | 2-4 | 23-51-14 | D05719J | | 6 | | GDY0009 | S.. | 2 | | ALL |
| 305R | 24 | PM | ME | | 0-0 | 23-51-14 | D05719J | | 5 | | TB0139H | 55 | 2 | | ALL |
| 305Y | 24 | PM | ME | | 0-0 | 23-51-14 | D05719J | | 7 | | TB0139H | 57 | 2 | | ALL |
| 306B | 24 | PM | B | | 4-0 | 23-31-12 | D00451 | | 18 | | D04625P | | 3 | | 050-099 |
| 306R | 24 | PM | B | | 0-0 | 23-31-12 | D00451 | | 14 | | D04625P | | 1 | | 050-099 |
| 306Y | 24 | PM | B | | 0-0 | 23-31-12 | D00451 | | 15 | | D04625P | | 2 | | 050-099 |
| 307B | 24 | PM | MG | | 6-2 | 23-41-11 | D05852P | | 3 | | TB0139G | 23 | 2 | | ALL |
| 307R | 24 | PM | MG | | 0-0 | 23-41-11 | D05852P | | 4 | | TB0139G | 22 | 2 | | ALL |
| 307Y | 24 | PM | MG | | 0-0 | 23-41-11 | D05852P | | 5 | | GDY0003 | S.. | 2 | | ALL |
| 401 | 20 | UA | | | 2-0 | 23-42-11 | D00459A | | | FA | GDX0001 | S.. | 2 | | ALL |
| 401B | 24 | PY | QA | | 4-0 | 23-42-11 | D00459A | D13 | | | TB0139F | C142 | 2 | | ALL |
| 401G | 24 | PY | QA | | 0-0 | 23-42-11 | D00459A | D15 | | | TB0139F | C143 | 2 | | ALL |
| 401R | 24 | PY | QA | | 0-0 | 23-42-11 | D00459A | D12 | | | TB0139F | A142 | 2 | | ALL |
| 401Y | 24 | PY | QA | | 0-0 | 23-42-11 | D00459A | D14 | | | TB0139F | A143 | 2 | | ALL |
| 401Z | | | QA | | 0-0 | 23-42-11 | D00459A | | | FA | TB0139F | C144 | 2 | | ALL |
| 402 | 20 | UA | | | 2-0 | 23-42-11 | D00459A | | | FB | GDX0001 | S.. | 2 | | ALL |
| 402B | 24 | PY | QB | | 2-9 | 23-42-11 | D00459A | A10 | | | D04615P | | 2 | | ALL |
| 402G | 24 | PY | QB | | 0-0 | 23-42-11 | D00459A | A12 | | | D04615P | | 4 | | ALL |
| 402R | 24 | PY | QB | | 0-0 | 23-42-11 | D00459A | A09 | | | D04615P | | 1 | | ALL |
| 402Y | 24 | PY | QB | | 0-0 | 23-42-11 | D00459A | A11 | | | D04615P | | 3 | | ALL |
| 402Z | | | QB | | 0-0 | 23-42-11 | D00459A | | | FB | D04615P | | 5 | | ALL |
| 403 | 20 | UA | | | 2-0 | 23-42-11 | D00459A | | | FC | GDX0001 | S.. | 2 | | ALL |
| 403B | 24 | PY | QC | | 3-0 | 23-42-11 | D00459A | D09 | | | D04629P | | 2 | | ALL |
| 403G | 24 | PY | QC | | 0-0 | 23-42-11 | D00459A | D11 | | | D04629P | | 4 | | ALL |
| 403R | 24 | PY | QC | | 0-0 | 23-42-11 | D00459A | D08 | | | D04629P | | 1 | | ALL |
| 403Y | 24 | PY | QC | | 0-0 | 23-42-11 | D00459A | D10 | | | D04629P | | 3 | | ALL |
| 403Z | | | QC | | 0-0 | 23-42-11 | D00459A | | | FC | D04629P | | 5 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 110

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | |
| 404 | 20 | | UA | 2-0 | 23-42-11 | D00459A | | | | FD | GDX0001 | S.. | 2 | ALL | |
| 404B | 24 | | PY QD | 3-0 | 23-42-11 | D00459A | A06 | | | | D04629P | 8 | | ALL | |
| 404G | 24 | | PY QD | 0-0 | 23-42-11 | D00459A | A08 | | | | D04629P | 10 | | ALL | |
| 404R | 24 | | PY QD | 0-0 | 23-42-11 | D00459A | A05 | | | | D04629P | 7 | | ALL | |
| 404Y | 24 | | PY QD | 0-0 | 23-42-11 | D00459A | A07 | | | | D04629P | 9 | | ALL | |
| 404Z | | | | 0-0 | 23-42-11 | D00459A | | | | FD | D04629P | 11 | | ALL | |
| 405 | 20 | | UA | 2-0 | 23-42-11 | D00459A | | | | FE | GDX0001 | S.. | 2 | ALL | |
| 405B | 24 | | PY QE | 3-4 | 23-42-11 | D00459A | D05 | | | | D04625P | 37 | | ALL | |
| 405G | 24 | | PY QE | 0-0 | 23-42-11 | D00459A | D07 | | | | D04625P | 39 | | ALL | |
| 405R | 24 | | PY QE | 0-0 | 23-42-11 | D00459A | D04 | | | | D04625P | 36 | | ALL | |
| 405Y | 24 | | PY QE | 0-0 | 23-42-11 | D00459A | D06 | | | | D04625P | 38 | | ALL | |
| 405Z | | | | 0-0 | 23-42-11 | D00459A | | | | FE | D04625P | 40 | | ALL | |
| 406 | 20 | | UA | 2-0 | 23-42-11 | D00459A | | | | FF | GDX0001 | S.. | 2 | ALL | |
| 406B | 24 | | PY QF | 3-4 | 23-42-11 | D00459A | A02 | | | | D04625P | 32 | | ALL | |
| 406G | 24 | | PY QF | 0-0 | 23-42-11 | D00459A | A04 | | | | D04625P | 34 | | ALL | |
| 406R | 24 | | PY QF | 0-0 | 23-42-11 | D00459A | A01 | | | | D04625P | 31 | | ALL | |
| 406Y | 24 | | PY QF | 0-0 | 23-42-11 | D00459A | A03 | | | | D04625P | 33 | | ALL | |
| 406Z | | | | 0-0 | 23-42-11 | D00459A | | | | FF | D04625P | 35 | | ALL | |
| 407 | 20 | | UA | 2-0 | SPARE | D00459A | | | | QG | GDX0001 | S.. | 2 | 150-199 | |
| 407B | 24 | | PY QG | 2-9 | SPARE | D00459A | A15 | | | | D04615P | 8 | | 150-199 | |
| 407G | 24 | | PY QG | 0-0 | SPARE | D00459A | B15 | | | | D04615P | 10 | | 150-199 | |
| 407R | 24 | | PY QG | 0-0 | SPARE | D00459A | A14 | | | | D04615P | 7 | | 150-199 | |
| 407Y | 24 | | PY QG | 0-0 | SPARE | D00459A | B14 | | | | D04615P | 9 | | 150-199 | |
| 407Z | | | | 0-0 | SPARE | D00459A | | | | QG | D04615P | 6 | | 150-199 | |
| 506 | 20 | | PA | 2-11 | 23-31-11 | D02267 | 44 | | | | GDX0005 | D.. | 2 | 050-099, 150-199 | |
| 507 | 24 | | PK | 3-2 | 23-31-11 | D02267 | 1 | | | | TB0139G | 106 | 2 | 050-099, 150-199 | |
| 508 | 24 | | PK | 3-3 | 23-31-11 | D02267 | 20 | | | | TB0139Z | 10 | BJ | 050-099, 150-199 | |
| 509 | 24 | | PK | 3-2 | 23-31-11 | D02267 | 32 | | | | TB0139G | 109 | 2 | 050-099 | |
| 509 | 24 | | PK | 3-2 | 23-31-11 | D02267 | 32 | | | | TB0139G | 19 | 2 | 150-199 | |
| 510 | 24 | | PK | 0-7 | 23-31-11 | TB0139G | 109 | 2 | | | TB0139D | A114 | 2 | 050-099 | |
| 510 | 24 | | PK | 3-2 | 23-31-11 | TB0139G | 19 | 2 | | | TB0139D | A114 | 2 | 150-199 | |
| 511 | 24 | | PV UK | 3-4 | 23-31-11 | D02271 | 2 | | | | D05421P | 13 | | 050-099, 150-199 | |
| 511Z | | | | 0-0 | 23-31-11 | D02271 | | | | UK | D05421P | 14 | | 050-099, 150-199 | |
| 512 | 20 | | PA | 3-2 | 23-31-11 | D05421P | 12 | | | | GDX0005 | S.. | 2 | 050-099, 150-199 | |
| 513 | 24 | | PK | 3-0 | 23-31-11 | D05421P | 16 | | | | TB0139D | C113 | 2 | 050-099, 150-199 | |
| 514 | 24 | | PK | 3-4 | 23-31-11 | D05421P | 15 | | | | D02271 | 21 | | 050-099, 150-199 | |
| 515 | 24 | | PK | 2-5 | 23-31-11 | D00459B | D11 | | | | TB0139D | C114 | 2 | 050-099, 150-199 | |
| 516 | 24 | | PK | 3-2 | 23-31-11 | D02271 | 1 | | | | TB0139G | 18 | 2 | 050-099, 150-199 | |
| 517 | 24 | | PK | 3-0 | 23-31-11 | TB0139D | A114 | 2 | | | TB0139D | A113 | 2 | 050-099, 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 111

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | |
| 518 | 20 | | PA | | 2-11 | 23-31-11 | D02271 | 15 | | | GDX0005 | S.. | 2 | | 050-099, 150-199 |
| 519 | 24 | | PK | | 3-0 | 23-31-11 | TB0139D | A001 | 2 | | TB0139D | A002 | 2 | | 050-099, 150-199 |
| 520 | 24 | | PK | | 3-0 | 23-31-11 | TB0139D | C114 | 2 | | TB0139D | C002 | 2 | | 050-099, 150-199 |
| 521 | 24 | | PK | | 3-0 | 23-31-11 | TB0139Z | 10 | BJ | | TB0139D | C001 | 2 | | 050-099, 150-199 |
| 522 | 20 | | PQ | UV | 3-2 | 23-31-11 | D02271 | 25 | | | TB0139H | 101 | 2 | | 050-099, 150-199 |
| 522Z | | | | UV | 0-0 | 23-31-11 | D02271 | DED | | | TB0139H | DED | | | 050-099, 150-199 |
| 523 | 24 | | PK | | 3-2 | 23-31-11 | D00459B | A09 | | | TB0139G | 18 | 2 | | 050-099, 150-199 |
| 524 | 24 | | PK | | 3-2 | 23-31-11 | D02271 | 17 | | | TB0139G | 110 | 2 | | 050-099 |
| 524 | 24 | | PK | | 3-2 | 23-31-11 | D02271 | 17 | | | TB0139G | 20 | 2 | | 150-199 |
| 525 | 24 | | PK | | 2-7 | 23-31-11 | TB0139D | A001 | 2 | | TB0139G | 110 | 2 | | 050-099 |
| 525 | 24 | | PK | | 3-3 | 23-31-11 | TB0139D | A001 | 2 | | TB0139G | 20 | 2 | | 150-199 |
| 526 | 20 | | PQ | VA | 3-10 | 23-31-13 | TB0139G | 34 | 2 | | D02271 | 37 | | | 050-099, 150-199 |
| 526Z | | | | VA | 0-0 | 23-31-13 | TB0139G | DED | | | D02271 | DED | | | 050-099, 150-199 |
| 527 | 20 | | PQ | VB | 3-10 | 23-31-13 | TB0139G | 34 | 2 | | D02271 | 30 | | | 050-099, 150-199 |
| 527Z | | | | VB | 0-0 | 23-31-13 | TB0139G | DED | | | D02271 | DED | | | 050-099, 150-199 |
| 528 | 24 | | PK | | 2-6 | 23-31-12 | D00451 | 56 | | | TB0139D | A140 | 2 | | 050-099, 150-199 |
| 529 | 20 | | PQ | VD | 3-10 | 23-31-13 | TB0139G | 34 | 2 | | D02271 | 24 | | | 050-099, 150-199 |
| 529Z | | | | VD | 0-0 | 23-31-13 | TB0139G | DED | | | D02271 | DED | | | 050-099, 150-199 |
| 532 | 24 | | PK | | 0-7 | 23-31-13 | TB0139D | A005 | 2 | | TB0139D | A015 | 2 | | 051-099, 151-153 |
| 533 | 24 | | PK | | 3-11 | 23-31-13 | TB0139D | C007 | 2 | | TB0139G | 32 | 2 | | 050, 150, 154-199 |
| 533 | 24 | | PK | | 3-11 | 23-31-13 | TB0139D | C005 | 2 | | TB0139G | 32 | 2 | | 051-099, 151-153 |
| 534 | 24 | | PK | | 4-1 | 23-31-13 | D05421P | 20 | | | TB0139G | 32 | 2 | | 050-099, 150-199 |
| 535 | 24 | | PK | | 0-7 | 23-31-13 | TB0139D | C005 | 2 | | TB0139D | C006 | 2 | | 051-099, 151-153 |
| 536 | 24 | | PK | | 0-7 | 23-31-13 | TB0139D | A006 | 2 | | TB0139D | A007 | 2 | | 051-099, 151-153 |
| 537 | 24 | | PK | | 0-7 | 23-31-13 | TB0139D | C008 | 2 | | TB0139D | C007 | 2 | | 051-099, 151-153 |
| 538 | 24 | | PK | | 4-1 | 23-31-13 | D05421P | 21 | | | TB0139G | 33 | 2 | | 050-099, 150-199 |
| 539 | 24 | | PK | | 3-11 | 23-31-13 | TB0139D | C008 | 2 | | TB0139G | 33 | 2 | | 051-099, 151-153 |
| 540 | 24 | | PK | | 1-1 | 23-31-13 | TB0139D | A008 | 2 | | TB0139D | A115 | 2 | | 051-099, 151-153 |
| 541 | 24 | | PK | | 1-1 | 23-31-13 | TB0139D | C115 | 2 | | TB0139D | C015 | 2 | | 051-099, 151-153 |
| 542 | 24 | | PK | | 3-2 | 23-31-13 | TB0139D | C115 | 2 | | TB0139G | 24 | 2 | | 050, 150, 154-199 |
| 542 | 24 | | PK | | 3-3 | 23-31-13 | TB0139D | C015 | 2 | | TB0139G | 24 | 2 | | 051-099, 151-153 |
| 543 | 24 | | PK | | 3-5 | 23-31-13 | D05421P | 22 | | | TB0139G | 24 | 2 | | 050-099, 150-199 |
| 544 | 24 | | PK | | 3-9 | 23-31-13 | D02271 | 16 | | | TB0139D | A139 | 2 | | 050-099, 150-199 |
| 545 | 24 | | PK | | 3-9 | 23-31-13 | D02271 | 29 | | | TB0139D | A138 | 2 | | 050-099, 150-199 |
| 546 | 24 | | PK | | 3-2 | 23-31-13 | D02271 | 34 | | | TB0139D | A025 | 2 | | 050-099, 150-199 |
| 548 | 24 | | PK | | 3-4 | 23-31-14 | D02267 | 2 | | | D05421P | CAP | Y | | 050, 150, 154-199 |
| 548 | 24 | | PK | | 3-4 | 23-31-14 | D02267 | 2 | | | D05421P | 17 | | | 051-099, 151-153 |
| 549 | 24 | | PK | | 3-2 | 23-31-14 | D02269 | 8 | | | TB0139G | 110 | 2 | | 050-099 |
| 549 | 24 | | PK | | 3-2 | 23-31-14 | D02269 | 8 | | | TB0139G | 20 | 2 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 112

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | | | | |
| 550 | 24 | | PK | | 3-3 | 23-31-14 | D02269 | | 17 | | | | | TB0139G | 16 | 2 | | 050-099, 150-199 |
| 551 | 24 | | PK | | 1-1 | 23-31-14 | TB0139D | | C113 | 2 | | | | TB0139G | 16 | 2 | | 050-099, 150-199 |
| 552 | 24 | | PK | | 3-3 | 23-31-14 | D02269 | | 16 | | | | | TB0139D | A007 | 2 | | 050-099, 150-199 |
| 553 | 24 | | PK | | 3-3 | 23-31-14 | D02269 | | 29 | | | | | TB0139D | A005 | 2 | | 050-099, 150-199 |
| 554 | 24 | | PK | | 3-2 | 23-31-14 | D02269 | | 34 | | | | | TB0139D | A115 | 2 | | 050-099, 150-199 |
| 555 | 20 | | PQ | WE | 3-3 | 23-31-14 | D02269 | | 37 | | | | | TB0139Z | 12 | BJ | | 050-099, 150-199 |
| 555Z | | | | WE | 0-0 | 23-31-14 | D02269 | | DED | | | | | TB0139Z | DED | | | 050-099, 150-199 |
| 556 | 20 | | PQ | WF | 3-3 | 23-31-14 | D02269 | | 30 | | | | | TB0139Z | 12 | BJ | | 050-099, 150-199 |
| 556Z | | | | WF | 0-0 | 23-31-14 | D02269 | | DED | | | | | TB0139Z | DED | | | 050-099, 150-199 |
| 557 | 20 | | PQ | WG | 3-3 | 23-31-14 | D02269 | | 24 | | | | | TB0139Z | 12 | BJ | | 050-099, 150-199 |
| 557Z | | | | WG | 0-0 | 23-31-14 | D02269 | | DED | | | | | TB0139Z | DED | | | 050-099, 150-199 |
| 558 | 20 | | PQ | WH | 6-6 | 23-31-14 | D02269 | | 25 | | | | | TB0139Z | CAP | Y | | 050-099 |
| 558 | 20 | | PQ | WH | 3-3 | 23-31-14 | D02269 | | 25 | | | | | TB0139Z | 12 | BJ | | 150-199 |
| 558Z | | | | WH | 0-0 | 23-31-14 | D02269 | | DED | | | | | TB0139Z | DED | | | 050-099, 150-199 |
| 559 | 20 | | PQ | WI | 3-3 | 23-31-14 | D02269 | | 5 | | | | | TB0139Z | 12 | BJ | | 050-099, 150-199 |
| 559Z | | | | WI | 0-0 | 23-31-14 | D02269 | | DED | | | | | TB0139Z | DED | | | 050-099, 150-199 |
| 560 | 20 | | PQ | WJ | 3-0 | 23-31-14 | TB0139Z | | 12 | BJ | | | | TB0139H | 101 | 2 | | 050-099, 150-199 |
| 560Z | | | | WJ | 0-0 | 23-31-14 | TB0139H | | DED | | | | | TB0139Z | DED | | | 050-099, 150-199 |
| 561 | 20 | | UA | | 2-11 | 23-31-11 | D02271 | | | | | UK | | GDX0005 | S.. | 2 | | 050-099, 150-199 |
| 565 | 24 | | PK | | 3-7 | 23-31-13 | TB0139D | | C025 | 2 | | | | TB0139G | 32 | 2 | | 050-099, 150-199 |
| 566 | 24 | | PK | | 3-2 | 23-31-13 | TB0139D | | C116 | 2 | | | | TB0139G | 24 | 2 | | 050-099, 150-199 |
| 567 | 24 | | PK | | 3-6 | 23-31-13 | TB0139D | | C121 | 2 | | | | TB0139G | 33 | 2 | | 050-099, 150-199 |
| 568 | 24 | | PK | | 0-7 | 23-31-13 | TB0139D | | A025 | 2 | | | | TB0139D | A017 | 2 | | 050-099, 150-199 |
| 570 | 24 | | PK | | 3-9 | 23-31-13 | TB0139D | | A116 | 2 | | | | TB0139D | A139 | 2 | | 050-099, 150-199 |
| 571 | 24 | | PK | | 3-5 | 23-31-13 | TB0139D | | A121 | 2 | | | | TB0139D | A138 | 2 | | 050-099, 150-199 |
| 572 | 24 | | PK | | 3-6 | 23-31-13 | TB0139D | | C017 | 2 | | | | TB0139H | 133 | 2 | | 050-099, 150-199 |
| 573 | 24 | | PK | | 0-7 | 23-31-13 | TB0139H | | 133 | 2 | | | | TB0139D | C139 | 2 | | 050-099, 150-199 |
| 574 | 24 | | PK | | 0-7 | 23-31-13 | TB0139H | | 133 | 2 | | | | TB0139D | C138 | 2 | | 050-099, 150-199 |
| 576 | 24 | | PK | | 4-6 | 23-31-12 | D04625P | | 10 | | | | | TB0139D | C140 | 2 | | 050-099, 150-199 |
| 610 | 22 | | PA | | 6-2 | 23-32-12 | D05593P | | 18 | | | | | D04625P | 15 | | | 050-099, 150-199 |
| 611 | 22 | | PA | | 6-2 | 23-32-12 | D05593P | | 16 | | | | | D04625P | 16 | | | 050-099, 150-199 |
| 612 | 22 | | PA | | 5-4 | 23-32-12 | D05593P | | 17 | | | | | D05421P | 19 | | | 050-099, 150-199 |
| 613 | 24 | | PK | | 4-10 | 23-42-11 | D04625P | | 52 | | | | | TB0139D | C157 | 2 | | 050-099 |
| 613 | 24 | | PK | | 4-10 | 23-42-11 | D04625P | | 25 | | | | | TB0139D | C157 | 2 | | 162-199 |
| 614 | 22 | | PA | | 4-9 | 23-42-11 | D04647P | | 26 | | | | | TB0139F | A156 | 2 | | 050-099 |
| 614 | 22 | | PA | | 5-1 | 23-42-11 | D04647P | | 26 | | | | | TB0139F | A162 | 2 | | 162-199 |
| 615 | 22 | | PA | | 4-9 | 23-42-11 | D04647P | | 27 | | | | | TB0139F | C156 | 2 | | 050-099 |
| 615 | 22 | | PA | | 5-1 | 23-42-11 | D04647P | | 27 | | | | | TB0139F | C162 | 2 | | 162-199 |
| 616 | 22 | | PA | | 3-6 | 23-42-11 | D04647P | | 28 | | | | | TB0139F | A120 | 2 | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 113

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | |
| 622 | 22 | PQ | YV | | 3-2 | 23-42-11 | D04647P | | 25 | | TB0139H | 111 | 2 | | 050-099 |
| 622 | 22 | PQ | YV | | 3-6 | 23-42-11 | D04647P | | 25 | | TB0139Z | 122 | BJ | | 162-199 |
| 622Z | | | YV | | 0-0 | 23-42-11 | D04647P | | DED | | TB0139H | DED | | | 050-099 |
| 622Z | | | YV | | 0-0 | 23-42-11 | D04647P | | DED | | TB0139Z | DED | | | 162-199 |
| 623 | 22 | PQ | YW | | 3-4 | 23-42-11 | D04625P | | 6 | | TB0139H | 111 | 2 | | 050-099 |
| 623 | 22 | PQ | YW | | 3-8 | 23-42-11 | D04625P | | 6 | | TB0139Z | 122 | BJ | | 162-199 |
| 623Z | | | YW | | 0-0 | 23-42-11 | D04625P | | DED | | TB0139H | DED | | | 050-099 |
| 623Z | | | YW | | 0-0 | 23-42-11 | D04625P | | DED | | TB0139Z | DED | | | 162-199 |
| 701 | 20 | PA | | | 3-2 | 23-34-13 | D02557 | | X2 | | GDY0011 | D.. | 2 | | 275-299 |
| 702 | 24 | PK | | | 4-6 | 23-34-13 | D04625P | | 51 | | TB0139G | 140 | 2 | | 275-278 |
| 702 | 24 | PK | | | 4-4 | 23-34-13 | D04625P | | 51 | | TB0139G | 139 | 2 | | 280-299 |
| 703 | 24 | PK | | | 2-8 | 23-34-13 | D02557 | | X1 | | TB0139G | 140 | 2 | | 275-278 |
| 703 | 24 | PK | | | 2-10 | 23-34-13 | D02557 | | X1 | | TB0139G | 139 | 2 | | 280-299 |
| 704 | 24 | PK | | | 2-8 | 23-34-13 | D02555 | | X1 | | TB0139G | 140 | 2 | | 275-278 |
| 704 | 24 | PK | | | 2-10 | 23-34-13 | D02555 | | X1 | | TB0139G | 139 | 2 | | 280-299 |
| 705 | 20 | PA | | | 3-2 | 23-34-13 | D02555 | | X2 | | GDY0011 | D.. | 2 | | 275-299 |
| 706 | 24 | PK | | | 3-6 | 23-34-13 | D02555 | | C3 | | TB0139D | C188 | 2 | | 275-299 |
| 707 | 24 | PK | | | 2-8 | 23-34-13 | D02555 | | A3 | | TB0139G | 161 | 2 | | 275-299 |
| 708 | 24 | PK | | | 2-8 | 23-34-13 | D02555 | | D3 | | TB0139D | C158 | 2 | | 275-299 |
| 709 | 24 | PK | | | 3-6 | 23-34-13 | D02555 | | B3 | | TB0139D | A186 | 2 | | 275-299 |
| 710 | 24 | PK | | | 3-5 | 23-34-13 | TB0139G | | 161 | 2 | TB0139D | A188 | 2 | | 275-299 |
| 763 | 24 | PK | | | 3-0 | 23-34-13 | TB0139D | | A109 | 2 | TB0139D | A111 | 2 | | 150-199, 275-299 |
| 764 | 24 | PK | | | 3-0 | 23-34-13 | TB0139D | | A110 | 2 | TB0139D | A112 | 2 | | 150-199, 275-299 |
| 765 | 24 | PK | | | 3-2 | 23-34-13 | TB0139D | | C111 | 2 | D04647P | 17 | | | 150-154, 156-199 |
| 765 | 24 | PK | | | 3-2 | 23-34-13 | TB0139D | | C109 | 2 | D04647P | 17 | | | 155, 275-299 |
| 766 | 24 | PK | | | 3-2 | 23-34-13 | TB0139D | | C112 | 2 | D04647P | 18 | | | 150-154, 156-199 |
| 766 | 24 | PK | | | 3-2 | 23-34-13 | TB0139D | | C110 | 2 | D04647P | 18 | | | 155, 275-299 |
| 768 | 24 | PK | | | 3-2 | 23-34-13 | TB0139D | | C111 | 2 | D04647P | 19 | | | 150-199, 275-299 |
| 769 | 24 | PK | | | 3-2 | 23-34-13 | TB0139D | | C112 | 2 | D04647P | 20 | | | 150-199, 275-299 |
| 775 | 24 | PK | | | 4-4 | 23-34-13 | TB0139D | | C110 | # | TB0139D | C158 | 2 | | 150-199 |
| 775 | 24 | PK | | | 4-4 | 23-34-13 | TB0139D | | C110 | 2 | TB0139D | C158 | 2 | | 275-299 |
| 776 | 24 | PK | | | 4-11 | 23-34-12 | D05421P | | 9 | | TB0139F | A070 | 2 | | ALL |
| 777 | 24 | PK | | | 4-11 | 23-34-12 | D05421P | | 10 | | TB0139F | C070 | 2 | | ALL |
| 778 | 24 | PK | | | 5-5 | 23-34-12 | D05421P | | 11 | | TB0139F | A091 | 2 | | ALL |
| 779 | 24 | PK | | | 6-3 | 23-34-13 | D05421P | | 5 | | TB0139G | 194 | 2 | | 050-099 |
| 779 | 24 | PK | | | 4-11 | 23-34-13 | D05421P | | 5 | | TB0139G | 68 | 2 | | 150-199, 275-299 |
| 780 | 24 | PK | | | 4-11 | 23-34-13 | D05421P | | 6 | | TB0139G | 69 | 2 | | 150-199, 275-299 |
| 781 | 24 | PK | | | 3-0 | 23-34-13 | D05421P | | 7 | | TB0139D | A111 | 2 | | 150-199 |
| 781 | 24 | PK | | | 4-2 | 23-34-13 | D05421P | | 7 | | D02557 | A2 | | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0140
Page 114
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | | |
| 782 | 24 | | PK | | 3-0 | 23-34-13 | D05421P | | 8 | | | TB0139D | A112 | 2 | | 150-199 |
| 782 | 24 | | PK | | 4-2 | 23-34-13 | D05421P | | 8 | | | D02557 | B2 | | | 275-299 |
| 783 | 24 | | PK | | 3-2 | 23-34-13 | TB0139G | | 189 | # | | TB0139G | 68 | 2 | | 150-199 |
| 783 | 24 | | PK | | 4-0 | 23-34-13 | D02557 | | A3 | | | TB0139D | A111 | 2 | | 275-299 |
| 784 | 24 | | PK | | 5-1 | 23-34-13 | TB0139D | | C109 | # | | TB0139D | C188 | 2 | | 150-199 |
| 784 | 24 | | PK | | 5-1 | 23-34-13 | TB0139D | | C109 | 2 | | TB0139D | C188 | 2 | | 275-299 |
| 785 | 24 | | PK | | 3-2 | 23-34-13 | TB0139G | | 191 | # | | TB0139G | 69 | 2 | | 150-199 |
| 785 | 24 | | PK | | 4-0 | 23-34-13 | D02557 | | B3 | | | TB0139D | A112 | 2 | | 275-299 |
| 786 | 24 | | PK | | 3-5 | 23-34-13 | TB0139D | | A158 | 2 | | TB0139D | A186 | 2 | | 150-154, 156-199, 275-299 |
| 786 | 24 | | PK | | 4-4 | 23-34-13 | TB0139D | | A158 | 2 | | TB0139D | A110 | 2 | | 155 |
| 787 | 24 | | PK | | 6-2 | 23-34-13 | D04625P | | 54 | | | TB0139D | A188 | 2 | | 150-154, 156-199 |
| 787 | 24 | | PK | | 3-4 | 23-34-13 | D04625P | | 54 | | | TB0139D | A109 | 2 | | 155 |
| 787 | 24 | | PK | | 4-6 | 23-34-13 | D04625P | | 54 | | | D02555 | C2 | | | 275-299 |
| 788 | 24 | | PK | | 4-10 | 23-34-13 | D04625P | | 55 | | | TB0139D | A158 | 2 | | 150-199 |
| 788 | 24 | | PK | | 4-6 | 23-34-13 | D04625P | | 55 | | | D02555 | D2 | | | 275-299 |
| 789 | 24 | | PK | | 6-2 | 23-34-13 | D04625P | | 24 | | | TB0139G | 189 | 2 | | 050-099, 150-199 |
| 789 | 24 | | PK | | 6-2 | 23-34-13 | D04625P | | 24 | | | TB0139F | A190 | 2 | | 275-299 |
| 790 | 24 | | PK | | 6-2 | 23-34-13 | D04625P | | 30 | | | TB0139G | 191 | 2 | | 050-099, 150-199 |
| 790 | 24 | | PK | | 6-2 | 23-34-13 | D04625P | | 30 | | | TB0139F | C190 | 2 | | 275-299 |
| 791 | 24 | | PK | | 6-2 | 23-34-13 | D04625P | | 52 | | | TB0139F | A187 | 2 | | 150-199 |
| 791 | 24 | | PK | | 4-6 | 23-34-13 | D04625P | | 52 | | | D02555 | A2 | | | 275-299 |
| 792 | 24 | | PK | | 6-2 | 23-34-13 | D04625P | | 53 | | | TB0139F | C187 | 2 | | 150-199 |
| 792 | 24 | | PK | | 4-6 | 23-34-13 | D04625P | | 53 | | | D02555 | B2 | | | 275-299 |
| 793 | 24 | | PK | | 6-2 | 23-34-13 | D04625P | | 26 | | | TB0139G | 190 | 2 | | 050-099 |
| 793 | 24 | | PK | | 6-2 | 23-34-13 | D04625P | | 26 | | | TB0139F | A190 | 2 | | 150-199 |
| 793 | 24 | | PK | | 6-2 | 23-34-13 | D04625P | | 26 | | | TB0139G | 189 | 2 | | 275-299 |
| 794 | 24 | | PK | | 6-7 | 23-34-13 | D04625P | | 27 | | | TB0139G | 192 | 2 | | 050-099 |
| 794 | 24 | | PK | | 6-2 | 23-34-13 | D04625P | | 27 | | | TB0139F | C190 | 2 | | 150-199 |
| 794 | 24 | | PK | | 6-2 | 23-34-13 | D04625P | | 27 | | | TB0139G | 191 | 2 | | 275-299 |
| 795 | 24 | | PK | | 5-2 | 23-34-13 | D04647P | | 8 | | | TB0139G | 68 | 2 | | 150-199, 275-299 |
| 796 | 24 | | PK | | 6-5 | 23-34-13 | D04647P | | 8 | | | TB0139G | 194 | 2 | | 050-099 |
| 796 | 24 | | PK | | 5-2 | 23-34-13 | D04647P | | 9 | | | TB0139G | 69 | 2 | | 150-199, 275-299 |
| 797 | 24 | | PK | | 6-0 | 23-34-13 | D04647P | | 21 | | | TB0139G | 189 | 2 | | ALL |
| 798 | 24 | | PK | | 6-0 | 23-34-13 | D04647P | | 22 | | | TB0139G | 191 | 2 | | ALL |
| 799 | 24 | | PK | | 6-0 | 23-34-13 | TB0139D | | C188 | 2 | | D04647P | 15 | | | 150-199 |
| 799 | 24 | | PK | | 4-9 | 23-34-13 | TB0139G | | 161 | 2 | | D04647P | 15 | | | 275-299 |
| 800 | 24 | | PK | | 6-0 | 23-34-13 | D04647P | | 16 | | | TB0139D | C186 | 2 | | 150-199, 275-299 |
| 801 | 24 | | PK | | 6-5 | 23-34-13 | D04647P | | 6 | | | TB0139G | 195 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 115

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0149 | 286T0149 | | | E2-5 SHELF,RIGHT (continued) | | | | | | | | | | | | | |
| 801 | 24 | | PK | 6-0 | 23-34-13 | D04647P | | 6 | | | | | TB0139G | 189 | 2 | | 150-154, 156-199, 275-299 |
| 801 | 24 | | PK | 6-0 | 23-34-13 | D04647P | | 6 | | | | | TB0139F | A190 | 2 | | 155 |
| 802 | 24 | | PK | 6-5 | 23-34-13 | D04647P | | 7 | | | | | TB0139G | 192 | 2 | | 050-099 |
| 802 | 24 | | PK | 6-0 | 23-34-13 | D04647P | | 7 | | | | | TB0139G | 191 | 2 | | 150-154, 156-199, 275-299 |
| 802 | 24 | | PK | 6-0 | 23-34-13 | D04647P | | 7 | | | | | TB0139F | C190 | 2 | | 155 |
| 803 | 24 | | PK | 3-0 | 23-34-13 | TB0139D | | A186 | 2 | | | | TB0139F | C187 | 2 | | 150-199 |
| 804 | 24 | | PK | 3-0 | 23-34-13 | TB0139G | | 191 | 2 | | | | TB0139G | 192 | 2 | | 050-099 |
| 804 | 24 | | PK | 0-7 | 23-34-13 | TB0139G | | 191 | 2 | | | | TB0139F | C190 | 2 | | 150-154, 156-199 |
| 805 | 24 | | PK | 0-7 | 23-34-13 | TB0139G | | 189 | 2 | | | | TB0139G | 190 | 2 | | 050-099 |
| 805 | 24 | | PK | 0-7 | 23-34-13 | TB0139G | | 189 | 2 | | | | TB0139F | A190 | 2 | | 150-154, 156-199 |
| 806 | 24 | | PK | 0-7 | 23-34-13 | TB0139D | | A188 | 2 | | | | TB0139F | A187 | 2 | | 150-199 |
| 808 | 24 | | PK | 2-10 | 23-31-12 | TB0139H | | 133 | 2 | | | | TB0139D | C140 | 2 | | 050-099, 150-199 |
| 809 | 24 | | PK | 4-5 | 23-34-13 | D02645 | | B1 | | | | | TB0139G | 195 | 2 | | 050-099 |
| 810 | 24 | | PK | 4-5 | 23-34-13 | D02645 | | A1 | | | | | TB0139G | 195 | 2 | | 050-099 |
| 811 | 24 | | PK | 3-3 | 23-34-13 | D02645 | | A2 | | | | | TB0139G | 108 | 2 | | 050-099 |
| 812 | 24 | | PK | 3-3 | 23-34-13 | D02645 | | B2 | | | | | TB0139G | 108 | 2 | | 050-099 |
| 813 | 24 | | PK | 4-0 | 23-34-13 | D02645 | | X1 | | | | | TB0139G | 190 | 2 | | 050-099 |
| 815 | 20 | | PA | 1-10 | 23-34-13 | D02645 | | X2 | | | | | GDX0005 | D.. | 2 | | 050-099 |
| 900 | 20 | | PA | 5-0 | 23-32-21 | TB0139G | | 21 | 2 | | | | D04625P | 1 | | | 150, 152-199 |
| 9001 | 24 | | PK | 4-4 | 23-31-14 | D02269 | | 3 | | | | | TB0139D | A152 | 2 | | 050-099, 150-199 |
| 9002 | 24 | | PK | 4-6 | 23-31-13 | D05421P | | 18 | | | | | TB0139D | A152 | 2 | | 050-099, 150-199 |
| 9003 | 24 | | PK | 4-5 | 23-31-13 | TB0139G | | 16 | 2 | | | | TB0139D | C152 | 2 | | 050-099, 150-199 |
| 9004 | 24 | | PK | 3-2 | 23-31-14 | D02269 | | 6 | | | | | TB0139G | 21 | 2 | | 050-099, 150-199 |
| 901 | 20 | | PA | 5-0 | 23-32-21 | GDX0005 | | S.. | 2 | | | | D04625P | 2 | | | 150, 152-199 |
| 905 | 24 | | PK | 3-1 | 23-31-13 | D05421P | | 17 | | | | | TB0139D | C005 | 2 | | 050 |
| 905 | 24 | | PK | 3-1 | 23-31-13 | D05421P | | 17 | 2 | | | | TB0139D | C005 | 2 | | 150, 154-199 |
| FRH | | | | 0-0 | 23-31-12 | D04625P | | | | | FH | | D04625P | 7 | | | 150-199, 275-299 |
| FRI | | | | 0-0 | 23-31-12 | D04625P | | | | | FI | | D04625P | 8 | | | 275-299 |
| FRK | | | | 0-0 | 23-32-12 | D04625P | | | | | FK | | D04625P | 9 | | | 275-299 |
| FRL | | | | 0-0 | 23-32-12 | D04625P | | | | | FL | | D04625P | 10 | | | 275-299 |
| FRM | | | | 0-0 | 23-32-12 | D05421P | | | | | FM | | D05421P | 12 | | | 275-299 |
| FRN | | | | 0-0 | 23-32-12 | D05593P | | | | | FN | | D05593P | 16 | | | 275-299 |
| FRO | | | | 0-0 | 23-32-12 | D05593P | | | | | FO | | D05593P | 24 | | | 275-299 |
| FRP | | | | 0-0 | 23-32-12 | D05593P | | | | | FP | | D05593P | 19 | | | 275-299 |
| PA1 | | | | 0-0 | | D02267 | | 15 | | | | | D02267 | 16 | | | 050-099, 150-199 |
| PA2 | | | | 0-0 | | D02269 | | 19 | | | | | D02269 | 20 | | | 050-099, 150-199 |
| PA3 | | | | 0-0 | | D02271 | | 19 | | | | | D02271 | 20 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0140

Page 116 End

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0150 | 286T0150 | | | P6-5-L2-MN PWR DISTR PNL | | | | | | | | | | | | | |
| 001 | 22 | PA | | 6-0 | 33-16-12 | D06154J | | 2 | | | | | C00102 | 1 | D | *1 | ALL |
| 002 | 22 | PA | | 7-0 | 33-16-12 | TB0018Y | A014 | BJ | | | | | C00102 | 1 | D | *1 | ALL |
| 004 | 22 | PA | | 6-0 | 33-16-12 | D06166J | | 2 | | | | | C00102 | 2 | D | | ALL |
| 005 | 22 | PA | | 6-0 | 33-16-12 | D06154J | | 3 | | | | | C00104 | 1 | D | | ALL |
| 006 | 22 | PA | | 8-0 | 33-16-12 | D06166J | | 3 | | | | | TB0018X | A002 | BJ | | ALL |
| 007 | 22 | PA | | 8-0 | 33-16-12 | D06166J | | 4 | | | | | TB0018Y | A014 | BJ | | ALL |
| 008 | 22 | PQ | A | 6-0 | 33-16-12 | D06166J | | 5 | | | | | C00103 | 2 | D | *1 | ALL |
| 008Z | | | A | 0-0 | 33-16-12 | D06166J | | DED | | | | | C00103 | DED | | | ALL |
| 009 | 22 | PQ | B | 6-0 | 33-16-12 | TB0018Y | C014 | BJ | | | | | C00103 | 2 | D | *1 | ALL |
| 009Z | | | B | 0-0 | 33-16-12 | TB0018Y | DED | | | | | | C00103 | DED | | | ALL |
| 010 | 22 | PQ | C | 8-0 | 33-16-12 | TB0018Y | C014 | BJ | | | | | D06154J | 4 | | | ALL |
| 010Z | | | C | 0-0 | 33-16-12 | TB0018Y | DED | | | | | | D06154J | DED | | | ALL |
| 011 | 22 | PQ | D | 8-0 | 33-16-12 | TB0018Y | C014 | BJ | | | | | D06166J | 6 | | | ALL |
| 011Z | | | D | 0-0 | 33-16-12 | TB0018Y | DED | | | | | | D06166J | DED | | | ALL |
| 012 | 22 | PQ | E | 8-0 | 33-16-12 | TB0018Y | C014 | BJ | | | | | D06166J | 7 | | | ALL |
| 012Z | | | E | 0-0 | 33-16-12 | TB0018Y | DED | | | | | | D06166J | DED | | | ALL |
| 013 | 22 | PQ | F | 6-0 | 33-16-12 | C00103 | | 1 | D | | | | D06166J | 8 | | | ALL |
| 013Z | | | F | 0-0 | 33-16-12 | C00103 | DED | | | | | | D06166J | DED | | | ALL |
| 014 | 22 | PQ | K | 6-0 | 33-16-22 | C00117 | | 1 | D | | | | D06166J | 10 | | | ALL |
| 014Z | | | K | 0-0 | 33-16-22 | C00117 | DED | | | | | | D06166J | DED | | | ALL |
| 015 | 22 | PA | | 6-0 | 33-16-22 | C00117 | | 2 | D | | | | D06154J | 13 | | | ALL |
| 017 | 22 | PQ | G | 4-0 | 33-16-22 | D06154J | | 16 | | | | | D06166J | 11 | | | ALL |
| 017Z | | | G | 0-0 | 33-16-22 | D06154J | DED | | | | | | D06166J | DED | | | ALL |
| 020 | 24 | PV | H | 8-0 | 24-51-71 | TB0022Y | A008 | BJ | | | | | D06154J | 20 | | | ALL |
| 020Z | | | H | 0-0 | 24-51-71 | TB0022Y | DED | | | | | | D06154J | DED | | | ALL |
| 021 | 24 | PV | I | 8-0 | 24-51-71 | TB0022Y | C008 | BJ | | | | | D06154J | 21 | | | ALL |
| 021Z | | | I | 0-0 | 24-51-71 | TB0022Y | DED | | | | | | D06154J | DED | | | ALL |
| 023 | 16 | PQ | L | 3-0 | 33-13-18 | D10658 | A3 | | | | | | TB0018F | A013 | 2 | | ALL |
| 023Z | | | L | 0-0 | 33-13-18 | D10658 | DED | | | | | | TB0018F | DED | | | ALL |
| 024 | 16 | PA | | 8-0 | 33-13-18 | D10658 | A2 | | | | | | D06166J | 16 | FM | | ALL |
| 025 | 16 | PA | | 8-0 | 33-13-18 | D10658 | A1 | | | | | | D06166J | 12 | FM | | ALL |
| 026 | 24 | PK | | 8-0 | 33-13-18 | D10658 | X1 | | | | | | D06166J | 14 | | | ALL |
| 027 | 20 | PA | | 3-0 | 33-13-18 | D10658 | X2 | | | | | | GD02418 | A.. | 2 | | ALL |
| 037 | 16 | PA | | 7-0 | 33-13-18 | D06166J | | 18 | FM | | | | GD02422 | A.. | 2 | | 156-157, 166-199, 277-299 |
| W0151 | 286T0151 | | | E2-1 SHELF | | | | | | | | | | | | | |
| 001 | 22 | PA | | 3-0 | 22-22-21 | D00667A | G12 | | | | | | D05293J | 4 | | | ALL |
| 002 | 22 | PA | | 3-0 | 22-22-21 | D00667B | J15 | | | | | | D05293J | 2 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0150

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0151 | 286T0151 | | | E2-1 SHELF (continued) | | | | | | | | | | | |
| 003 | 22 | | PA | 3-0 | 22-22-21 | D00667B | | J14 | | | D05293J | | 3 | | ALL |
| 004 | 22 | | PA | 4-0 | 22-21-21 | D01261B | | C15 | | | D05293J | | 1 | | ALL |
| 005 | 22 | | PA | 3-0 | 22-24-21 | D00667B | | H15 | | | D05293J | | 5 | | ALL |
| 006 | 16 | | PA | 4-0 | 27-09-11 | D01255C | | | 3 | | GDX0005 | D.. | 2 | | ALL |
| 007 | 16 | | PA | 4-0 | 27-09-11 | D01255C | | | 2 | | GDX0005 | D.. | 2 | | ALL |
| 008 | 16 | | PA | 4-0 | 27-09-11 | D01255C | | | 8 | | GDX0005 | S.. | 2 | | ALL |
| 009 | 16 | | PA | 4-0 | 27-09-11 | D01255C | | | 7 | | GDX0005 | D.. | 2 | | ALL |
| 010 | 16 | | PA | 4-0 | 27-09-11 | D01255C | | | 10 | | GDX0005 | D.. | 2 | | ALL |
| 011 | 16 | | PA | 4-0 | 27-09-11 | D01255C | | | 9 | | GDX0005 | D.. | 2 | | ALL |
| 012 | 16 | | PA | 4-0 | 27-09-11 | D01255C | | | 11 | | GDX0005 | A.. | 2 | | ALL |
| 013 | 20 | | PA | 4-0 | 27-61-12 | D00835C | | | 4 | | GDX0005 | D.. | 2 | | ALL |
| 014 | 20 | | PA | 4-0 | 27-61-12 | D00833C | | | 4 | | GDX0006 | D.. | 2 | | ALL |
| 015 | 16 | | PA | 5-0 | 27-09-11 | D01257C | | | 3 | | GDX0006 | D.. | 2 | | ALL |
| 016 | 16 | | PA | 5-0 | 27-09-11 | D01257C | | | 2 | | GDX0006 | D.. | 2 | | ALL |
| 017 | 16 | | PA | 5-0 | 27-09-11 | D01257C | | | 8 | | GDX0006 | S.. | 2 | | ALL |
| 018 | 16 | | PA | 5-0 | 27-09-11 | D01257C | | | 7 | | GDX0006 | D.. | 2 | | ALL |
| 019 | 16 | | PA | 5-0 | 27-09-11 | D01257C | | | 10 | | GDX0006 | D.. | 2 | | ALL |
| 020 | 16 | | PA | 5-0 | 27-09-11 | D01257C | | | 9 | | GDX0006 | D.. | 2 | | ALL |
| 021 | 16 | | PA | 5-0 | 27-09-11 | D01257C | | | 11 | | GDX0006 | A.. | 2 | | ALL |
| 022 | 22 | | PA | 5-0 | 27-09-12 | D01261B | | C14 | | | TB0141H | 29 | 2 | | ALL |
| 023 | 22 | | PA | 4-0 | 27-09-12 | D00667B | | K12 | | | TB0141H | 29 | 2 | | ALL |
| 024 | 22 | | PA | 5-0 | 27-09-12 | D00835B | | D02 | | | TB0141H | 29 | 2 | | ALL |
| 025 | 22 | | PA | 4-0 | 27-09-12 | D00833A | | D01 | | | TB0141H | 29 | 2 | | ALL |
| 026 | 22 | | PA | 4-0 | 27-09-12 | D00831B | | D10 | | | TB0141H | 29 | 2 | | ALL |
| 027 | 22 | | PA | 4-0 | 27-09-12 | D05293J | | | 6 | | TB0141H | 29 | 2 | | ALL |
| 028 | 22 | | PA | 4-0 | 27-09-13 | D05293J | | | 7 | | TB0141G | 129 | 2 | | ALL |
| 029 | 22 | | PA | 4-0 | 27-09-13 | D05293J | | | 8 | | TB0141G | 130 | 2 | | ALL |
| 030 | 22 | | PA | 4-0 | 27-09-13 | D00833A | | J13 | | | TB0141G | 129 | 2 | | ALL |
| 031 | 22 | | PA | 4-0 | 27-09-13 | D00833A | | K13 | | | TB0141G | 130 | 2 | | ALL |
| 032 | 22 | | PA | 4-0 | 27-09-13 | D00667B | | H05 | | | TB0141G | 129 | 2 | | ALL |
| 033 | 22 | | PA | 4-0 | 27-09-13 | D00667B | | H06 | | | TB0141G | 130 | 2 | | ALL |
| 034 | 22 | | PA | 4-0 | 27-21-22 | D01265B | | C15 | | | GDX0006 | D.. | 2 | | ALL |
| 035 | 22 | | PA | 4-0 | 27-21-22 | D01265B | | B15 | | | GDX0006 | D.. | 2 | | ALL |
| 036 | 22 | | PA | 3-0 | 27-21-22 | D01265B | | A15 | | | GDX0005 | D.. | 2 | | ALL |
| 037 | 16 | | PA | 3-0 | 27-21-22 | D01265C | | | 2 | | GDX0005 | S.. | 2 | | ALL |
| 038 | 16 | | PA | 3-0 | 27-21-22 | D01265C | | | 3 | | GDX0005 | D.. | 2 | | ALL |
| 039 | 22 | | PA | 3-0 | 27-21-22 | D01265B | | D15 | | | GDX0005 | D.. | 2 | | ALL |
| 040 | 16 | | PA | 3-0 | 27-21-22 | D01265C | | | 4 | | GDX0005 | D.. | 2 | | ALL |
| 044 | 22 | | PA | 5-0 | 27-61-11 | D00835B | | E02 | | | TB0141G | 31 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0150
Page 2
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0151 | 286T0151 | | | E2-1 SHELF (continued) | | | | | | | | | | | |
| 045 | 22 | | PA | | 4-0 | 27-61-11 | D00833A | E01 | | | TB0141G | 31 | 2 | | ALL |
| 046 | 22 | | PA | | 4-0 | 27-61-11 | D00831B | E10 | | | TB0141G | 31 | 2 | | ALL |
| 047 | 22 | | PA | | 4-0 | 27-61-11 | D05293J | 15 | | | TB0141G | 31 | 2 | | ALL |
| 048 | 22 | | PA | | 3-0 | 27-41-21 | D00667B | E10 | | | GDX0004 | D.. | 2 | | 150-199, 275-299 |
| 049 | 22 | | PA | | 5-0 | 27-61-17 | D00833A | E11 | | | D01255B | K01 | | | ALL |
| 050 | 22 | | PA | | 6-0 | 27-61-17 | D00833A | E12 | | | D01257B | K01 | | | ALL |
| 055 | 16 | | PA | | 4-0 | 27-61-13 | D00831C | 8 | | | GDX0007 | D.. | 2 | | ALL |
| 056 | 16 | | PA | | 4-0 | 27-61-13 | D00831C | 3 | | | GDX0007 | D.. | 2 | | ALL |
| 057 | 16 | | PA | | 4-0 | 27-61-13 | D00831C | 10 | | | GDX0007 | S.. | 2 | | ALL |
| 058 | 16 | | PA | | 4-0 | 27-61-13 | D00831C | 9 | | | GDX0007 | S.. | 2 | | ALL |
| 059 | 22 | | PA | | 6-0 | 27-61-13 | D00831B | F14 | | | D01257B | H03 | | | ALL |
| 060 | 22 | | PA | | 6-0 | 27-61-13 | D00831B | F12 | | | D01257B | F03 | | | ALL |
| 061 | 22 | | PA | | 3-0 | 27-61-13 | D01255B | H03 | | | D00831B | G14 | | | ALL |
| 062 | 22 | | PA | | 3-0 | 27-61-13 | D01255B | F03 | | | D00831B | G12 | | | ALL |
| 063 | 16 | | PA | | 4-0 | 27-61-17 | D00833C | 9 | | | GDX0010 | S.. | 2 | | ALL |
| 064 | 20 | | PA | | 4-0 | 27-61-17 | D00833C | 6 | | | GDX0010 | D.. | 2 | | ALL |
| 067 | 22 | | PA | | 4-0 | 27-41-21 | D00667B | H13 | | | GDX0010 | D.. | 2 | | 050-099 |
| 068 | 16 | | PA | | 4-0 | 27-61-17 | D00833C | 8 | | | GDX0010 | D.. | 2 | | ALL |
| 069 | 16 | | PA | | 4-0 | 27-61-17 | D00833C | 10 | | | GDX0007 | S.. | 2 | | ALL |
| 070 | 22 | | PA | | 5-0 | 27-61-17 | D01255B | F04 | | | D00833A | G03 | | | ALL |
| 071 | 22 | | PA | | 5-0 | 27-61-17 | D01255B | H04 | | | D00833A | G05 | | | ALL |
| 073 | 16 | | PA | | 4-0 | 27-61-17 | D00833C | 3 | | | GDX0007 | D.. | 2 | | ALL |
| 074 | 16 | | PA | | 4-0 | 27-61-17 | D00833C | 2 | | | GDX0007 | D.. | 2 | | ALL |
| 076 | 22 | | PA | | 6-0 | 27-61-17 | D00833A | F05 | | | D01257B | H04 | | | ALL |
| 077 | 22 | | PA | | 6-0 | 27-61-17 | D00833A | F03 | | | D01257B | F04 | | | ALL |
| 078 | 16 | | PA | | 3-0 | 27-61-18 | D00835C | 8 | | | GDX0010 | D.. | 2 | | ALL |
| 079 | 16 | | PA | | 3-0 | 27-61-18 | D00835C | 3 | | | GDX0010 | D.. | 2 | | ALL |
| 080 | 16 | | PA | | 3-0 | 27-61-18 | D00835C | 2 | | | GDX0010 | D.. | 2 | | ALL |
| 081 | 16 | | PA | | 3-0 | 27-61-18 | D00835C | 7 | | | GDX0010 | D.. | 2 | | ALL |
| 082 | 16 | | PA | | 3-0 | 27-61-18 | D00835C | 9 | | | GDX0010 | S.. | 2 | | ALL |
| 083 | 16 | | PA | | 4-0 | 27-61-17 | D00833C | 7 | | | GDX0010 | D.. | 2 | | ALL |
| 084 | 22 | | PA | | 6-0 | 27-61-18 | D01257B | A07 | | | D01255B | C07 | | | ALL |
| 085 | 22 | | PA | | 5-0 | 27-61-18 | D01257B | C05 | | | TB0141H | 133 | 2 | | ALL |
| 087 | 22 | | PA | | 6-0 | 27-61-18 | D00835B | G06 | | | D01255B | H05 | | | ALL |
| 088 | 22 | | PA | | 6-0 | 27-61-18 | D00835B | G04 | | | D01255B | F05 | | | ALL |
| 090 | 22 | | PA | | 4-0 | 27-61-18 | D00835B | F06 | | | D01257B | H05 | | | ALL |
| 091 | 22 | | PA | | 4-0 | 27-61-18 | D00835B | F04 | | | D01257B | F05 | | | ALL |
| 116 | 22 | | PA | | 4-0 | 27-41-21 | D00667B | H08 | | | GDX0007 | D.. | 2 | | ALL |
| 118 | 22 | | PA | | 4-0 | 27-41-21 | D00667B | H10 | | | GDX0007 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0150

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|-------|------|------|---------|-------------|---|--|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0151 | 286T0151 | | | E2-1 SHELF (continued) | | | | | | | | | | | | | | |
| 124 | 16 | | PA | | 4-0 | 27-41-21 | D00667C | | | 3 | | | | GDX0006 | D.. | 2 | | ALL |
| 125 | 16 | | PA | | 4-0 | 27-41-21 | D00667C | | | 2 | | | | GDX0006 | D.. | 2 | | ALL |
| 126 | 16 | | PA | | 4-0 | 27-41-21 | D00667C | | | 11 | | | | GDX0006 | D.. | 2 | | ALL |
| 127 | 16 | | PA | | 4-0 | 27-41-21 | D00667C | | | 8 | | | | GDX0006 | D.. | 2 | | ALL |
| 128 | 16 | | PA | | 4-0 | 27-41-21 | D00667C | | | 7 | | | | GDX0006 | D.. | 2 | | ALL |
| 129 | 16 | | PA | | 4-0 | 27-41-21 | D00667C | | | 10 | | | | GDX0007 | S.. | 2 | | ALL |
| 132 | 16 | | PA | | 4-0 | 27-61-18 | D00835C | | | 10 | | | | GDX0007 | S.. | 2 | | ALL |
| 133 | 20 | | PA | | 4-0 | 27-61-18 | D00835C | | | 6 | | | | GDX0007 | D.. | 2 | | ALL |
| 135 | 20 | | PA | | 4-0 | 27-61-12 | D00831C | | | 4 | | | | GDX0009 | D.. | 2 | | ALL |
| 137 | 20 | | PA | | 4-0 | 22-21-21 | D01261C | | | 1 | | | | GDX0007 | S.. | 2 | | ALL |
| 138 | 16 | | PA | | 4-0 | 22-21-21 | D01261C | | | 2 | | | | GDX0010 | D.. | 2 | | ALL |
| 139 | 16 | | PA | | 4-0 | 22-21-21 | D01261C | | | 3 | | | | GDX0010 | D.. | 2 | | ALL |
| 140 | 20 | | PA | | 4-0 | 22-21-21 | D01261C | | | 4 | | | | GDX0007 | S.. | 2 | | ALL |
| 141 | 20 | | PA | | 3-0 | 22-21-21 | D01261C | | | 6 | | | | GDX0009 | S.. | 2 | | ALL |
| 142 | 16 | | PA | | 3-0 | 22-21-21 | D01261C | | | 8 | | | | GDX0009 | S.. | 2 | | ALL |
| 143 | 16 | | PA | | 4-0 | 22-21-21 | D01261C | | | 9 | | | | GDX0010 | D.. | 2 | | ALL |
| 144 | 16 | | PA | | 4-0 | 22-21-21 | D01261C | | | 10 | | | | GDX0010 | D.. | 2 | | ALL |
| 148 | 22 | | PA | | 1-10 | 27-61-13 | D00831B | | D14 | | | | | D00831B | D15 | | | ALL |
| 149 | 22 | | PA | | 1-10 | 27-61-13 | D00831B | | B14 | | | | | D00831B | B15 | | | ALL |
| 150 | 16 | | PA | | 4-0 | 27-61-13 | D00831C | | | 2 | | | | GDX0009 | D.. | 2 | | ALL |
| 151 | 16 | | PA | | 4-0 | 27-61-13 | D00831C | | | 7 | | | | GDX0009 | D.. | 2 | | ALL |
| 152 | 20 | | PA | | 4-0 | 27-61-13 | D00831C | | | 6 | | | | GDX0009 | D.. | 2 | | ALL |
| 153 | 22 | | PA | | 2-1 | 27-61-17 | D00833A | | D02 | | | | | D00833A | D03 | | | ALL |
| 157 | 22 | | PA | | 2-1 | 27-61-17 | D00833A | | D04 | | | | | D00833A | D05 | | | ALL |
| 158 | 22 | | PA | | 2-1 | 27-61-17 | D00833A | | B04 | | | | | D00833A | B05 | | | ALL |
| 159 | 22 | | PA | | 1-0 | 27-61-18 | D00835B | | D03 | | | | | D00835B | D04 | | | ALL |
| 163 | 22 | | PA | | 1-0 | 27-61-18 | D00835B | | D05 | | | | | D00835B | D06 | | | ALL |
| 164 | 22 | | PA | | 1-0 | 27-61-18 | D00835B | | B05 | | | | | D00835B | B06 | | | ALL |
| 166 | 20 | | PA | | 4-0 | 27-61-13 | D00831C | | | 5 | | | | GDX0009 | D.. | 2 | | ALL |
| 167 | 20 | | PA | | 4-0 | 27-61-17 | D00833C | | | 5 | | | | GDX0007 | D.. | 2 | | ALL |
| 168 | 20 | | PA | | 4-0 | 27-61-18 | D00835C | | | 5 | | | | GDX0010 | D.. | 2 | | ALL |
| 169 | 22 | | PA | | 3-0 | 27-41-21 | D00667B | | E11 | | | | | GDX0004 | D.. | 2 | | 150-199, 275-299 |
| 170 | 22 | | PA | | 3-0 | 27-41-21 | D00667B | | G08 | | | | | GDX0004 | D.. | 2 | | ALL |
| 171 | 22 | | PA | | 3-0 | 27-41-21 | D00667B | | G09 | | | | | GDX0004 | D.. | 2 | | ALL |
| 172 | 22 | | PA | | 3-0 | 27-41-21 | D00667B | | G10 | | | | | GDX0004 | D.. | 2 | | ALL |
| 173 | 22 | | PA | | 3-0 | 27-41-21 | D00667B | | G11 | | | | | GDX0004 | D.. | 2 | | ALL |
| 174 | 22 | | PA | | 3-0 | 27-41-21 | D00667B | | G12 | | | | | GDX0004 | D.. | 2 | | ALL |
| 175 | 22 | | PA | | 3-0 | 27-41-21 | D00667B | | G13 | | | | | GDX0004 | D.. | 2 | | ALL |
| 176 | 22 | | PA | | 3-0 | 27-41-21 | D00667B | | G14 | | | | | GDX0004 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0150
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0151 | 286T0151 | | | E2-1 SHELF (continued) | | | | | | | | | | | | |
| 177 | 22 | | PA | 3-0 | 27-41-21 | D00667B | G15 | | | | | GDX0004 | D.. | 2 | | ALL |
| 178 | 22 | | PA | 3-0 | 27-61-17 | D00833A | C01 | | | | | D00667B | J12 | | | ALL |
| 179 | 22 | | PA | 3-0 | 27-41-21 | D00667B | H11 | | | | | GDX0007 | D.. | 2 | | ALL |
| 180 | 22 | | PA | 3-0 | 27-41-21 | D00667B | E13 | | | | | GDX0004 | D.. | 2 | | 150-199, 275-299 |
| 196 | 16 | | PA | 3-0 | 27-11-22 | D00667C | 9 | | | | | R00025 | =B | \$ | | ALL |
| 197 | 16 | | PA | 3-0 | 27-11-22 | GDX0010 | D.. | 2 | | | | R00025 | =A | \$ | | ALL |
| 201 | 20 | | UA | 0-18 | 22-22-21 | GDX0008 | S.. | 2 | | | | D05293J | | | FE | ALL |
| 201B | 24 | | PW IA | 3-0 | 22-22-21 | D05293J | 20 | | | | | D00667B | K15 | | | ALL |
| 201R | 24 | | PW IA | 0-0 | 22-22-21 | D05293J | 19 | | | | | D00667B | K14 | | | ALL |
| 201Z | | | IA | 0-0 | 22-22-21 | D05293J | | | | | FE | D00667B | DED | | | ALL |
| 202 | 20 | | UA | 0-18 | 22-21-21 | D05293J | | | | | FD | GDX0008 | S.. | 2 | | ALL |
| 202B | 24 | | PW IB | 4-0 | 22-21-21 | D01261B | A15 | | | | | D05293J | 10 | | | ALL |
| 202R | 24 | | PW IB | 0-0 | 22-21-21 | D01261B | A14 | | | | | D05293J | 9 | | | ALL |
| 202Z | | | IB | 0-0 | 22-21-21 | D01261B | DED | | | | | D05293J | | | FD | ALL |
| 203B | 22 | | PB IC | 4-0 | 27-61-13 | D00831B | J15 | | | | | TB0141H | 133 | 2 | | ALL |
| 203R | 22 | | PB IC | 0-0 | 27-61-13 | D00831B | K15 | | | | | TB0141H | 131 | 2 | | ALL |
| 204B | 22 | | PB ID | 4-0 | 27-61-17 | D00833A | G08 | | | | | D05485J | 3 | | | ALL |
| 204R | 22 | | PB ID | 0-0 | 27-61-17 | D00833A | G09 | | | | | D05485J | 1 | | | ALL |
| 205B | 22 | | PB IE | 4-0 | 27-61-17 | D00833A | J11 | | | | | TB0141G | 136 | 2 | | ALL |
| 205R | 22 | | PB IE | 0-0 | 27-61-17 | D00833A | K11 | | | | | TB0141G | 135 | 2 | | ALL |
| 206B | 22 | | PB IF | 4-0 | 27-61-17 | D00833A | G11 | | | | | D05485J | 11 | | | ALL |
| 206R | 22 | | PB IF | 0-0 | 27-61-17 | D00833A | G10 | | | | | D05485J | 10 | | | ALL |
| 207B | 22 | | PB IG | 4-0 | 27-61-17 | D00833A | J06 | | | | | TB0141H | 133 | 2 | | ALL |
| 207R | 22 | | PB IG | 0-0 | 27-61-17 | D00833A | K06 | | | | | TB0141H | 131 | 2 | | ALL |
| 208B | 22 | | PB IH | 4-0 | 27-61-17 | D05485J | 9 | | | | | TB0141G | 136 | 2 | | ALL |
| 208R | 22 | | PB IH | 0-0 | 27-61-17 | D05485J | 8 | | | | | TB0141G | 135 | 2 | | ALL |
| 209B | 22 | | PB II | 4-0 | 27-61-17 | D05485J | 15 | | | | | TB0141G | 136 | 2 | | ALL |
| 209R | 22 | | PB II | 0-0 | 27-61-17 | D05485J | 14 | | | | | TB0141G | 135 | 2 | | ALL |
| 210B | 22 | | PB IJ | 4-0 | 27-61-18 | D05141J | 9 | | | | | TB0141H | 133 | 2 | | ALL |
| 210R | 22 | | PB IJ | 0-0 | 27-61-18 | D05141J | 8 | | | | | TB0141H | 131 | 2 | | ALL |
| 211B | 22 | | PB IK | 4-0 | 27-61-18 | D05141J | 2 | | | | | TB0141H | 133 | 2 | | ALL |
| 211R | 22 | | PB IK | 0-0 | 27-61-18 | D05141J | 1 | | | | | TB0141H | 131 | 2 | | ALL |
| 212B | 22 | | PB IL | 5-0 | 27-61-18 | D01255B | C05 | | | | | TB0141H | 133 | 2 | | ALL |
| 212R | 22 | | PB IL | 0-0 | 27-61-18 | D01255B | A05 | | | | | TB0141H | 131 | 2 | | ALL |
| 213B | 22 | | PB IM | 5-0 | 27-61-18 | D00835B | J07 | | | | | TB0141H | 133 | 2 | | ALL |
| 213R | 22 | | PB IM | 0-0 | 27-61-18 | D00835B | K07 | | | | | TB0141H | 131 | 2 | | ALL |
| 301B | 22 | | PC MA | 5-0 | 27-61-13 | D00831B | J14 | | | | | TB0141G | 33 | 2 | | ALL |
| 301R | 22 | | PC MA | 0-0 | 27-61-13 | D00831B | J12 | | | | | TB0141G | 32 | 2 | | ALL |
| 301Y | 22 | | PC MA | 0-0 | 27-61-13 | D00831B | J13 | | | | | TB0141G | 34 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0150

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|---------------------------------|-------|-------------|----------|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0151 | 286T0151 | E2-1 SHELF (continued) | | | | | | | | | | | | | |
| 302B | 22 | PC | MB | 5-0 | 27-61-13 | D00831B | | K14 | | TB0141G | 36 | 2 | | ALL | |
| 302R | 22 | PC | MB | 0-0 | 27-61-13 | D00831B | | K12 | | TB0141G | 35 | 2 | | ALL | |
| 302Y | 22 | PC | MB | 0-0 | 27-61-13 | D00831B | | K13 | | TB0141G | 37 | 2 | | ALL | |
| 303B | 22 | PC | MC | 4-0 | 27-61-17 | D00833A | | J05 | | TB0141G | 33 | 2 | | ALL | |
| 303R | 22 | PC | MC | 0-0 | 27-61-17 | D00833A | | J03 | | TB0141G | 32 | 2 | | ALL | |
| 303Y | 22 | PC | MC | 0-0 | 27-61-17 | D00833A | | J04 | | TB0141G | 34 | 2 | | ALL | |
| 304B | 22 | PC | MD | 4-0 | 27-61-17 | D00833A | | K05 | | TB0141G | 36 | 2 | | ALL | |
| 304R | 22 | PC | MD | 0-0 | 27-61-17 | D00833A | | K03 | | TB0141G | 35 | 2 | | ALL | |
| 304Y | 22 | PC | MD | 0-0 | 27-61-17 | D00833A | | K04 | | TB0141G | 37 | 2 | | ALL | |
| 305B | 22 | PC | ME | 4-0 | 27-61-17 | D00833A | | K10 | | D05485J | 23 | | | ALL | |
| 305R | 22 | PC | ME | 0-0 | 27-61-17 | D00833A | | K08 | | D05485J | 5 | | | ALL | |
| 305Y | 22 | PC | ME | 0-0 | 27-61-17 | D00833A | | K09 | | D05485J | 7 | | | ALL | |
| 306B | 22 | PC | MF | 4-0 | 27-61-17 | D00833A | | J10 | | D05485J | 24 | | | ALL | |
| 306R | 22 | PC | MF | 0-0 | 27-61-17 | D00833A | | J08 | | D05485J | 12 | | | ALL | |
| 306Y | 22 | PC | MF | 0-0 | 27-61-17 | D00833A | | J09 | | D05485J | 13 | | | ALL | |
| 307B | 22 | PC | MG | 5-0 | 27-61-18 | D05141J | | 4 | | TB0141G | 33 | 2 | | ALL | |
| 307R | 22 | PC | MG | 0-0 | 27-61-18 | D05141J | | 6 | | TB0141G | 32 | 2 | | ALL | |
| 307Y | 22 | PC | MG | 0-0 | 27-61-18 | D05141J | | 7 | | TB0141G | 34 | 2 | | ALL | |
| 308B | 22 | PC | MH | 5-0 | 27-61-18 | D05141J | | 10 | | TB0141G | 36 | 2 | | ALL | |
| 308R | 22 | PC | MH | 0-0 | 27-61-18 | D05141J | | 3 | | TB0141G | 35 | 2 | | ALL | |
| 308Y | 22 | PC | MH | 0-0 | 27-61-18 | D05141J | | 5 | | TB0141G | 37 | 2 | | ALL | |
| 309B | 22 | PC | MI | 5-0 | 27-61-18 | D00835B | | J06 | | TB0141G | 33 | 2 | | ALL | |
| 309R | 22 | PC | MI | 0-0 | 27-61-18 | D00835B | | J04 | | TB0141G | 32 | 2 | | ALL | |
| 309Y | 22 | PC | MI | 0-0 | 27-61-18 | D00835B | | J05 | | TB0141G | 34 | 2 | | ALL | |
| 310B | 22 | PC | MJ | 5-0 | 27-61-18 | D00835B | | K06 | | TB0141G | 36 | 2 | | ALL | |
| 310R | 22 | PC | MJ | 0-0 | 27-61-18 | D00835B | | K04 | | TB0141G | 35 | 2 | | ALL | |
| 310Y | 22 | PC | MJ | 0-0 | 27-61-18 | D00835B | | K05 | | TB0141G | 37 | 2 | | ALL | |
| FRD | | | | 0-0 | 22-21-21 | D05293J | | 11 | | D05293J | | | | FD ALL | |
| FRE | | | | 0-0 | 22-22-21 | D05293J | | 21 | | D05293J | | | | FE ALL | |
| W0152 | 286T0152 | P6-5-R2-MN PWR DISTR PNL | | | | | | | | | | | | | |
| 001 | 20 | PA | | 8-0 | 33-11-14 | D06156J | | 2 | | TB0018Y | C005 | BJ | | ALL | |
| 003 | 24 | PK | | 3-0 | 33-16-11 | D10288 | | X1 | | TB0018Z | 9 | BJ | | ALL | |
| 004 | 24 | PK | | 3-0 | 33-16-11 | D10288 | | X2 | | TB0018Z | 10 | BJ | | ALL | |
| 005 | 20 | PA | | 2-0 | 33-16-11 | D10278 | | A2 | | GD02418 | D.. | 2 | | ALL | |
| 006 | 24 | PK | | 7-0 | 33-16-11 | D10278 | | A1 | | D06172J | 30 | | | ALL | |
| 007 | 24 | PK | | 3-0 | 33-16-11 | D10278 | | X1 | | TB0018Y | C006 | BJ | | ALL | |
| 008 | 24 | PK | | 3-0 | 33-16-11 | D10278 | | X2 | | TB0018Z | 11 | BJ | | ALL | |
| 009 | 24 | PK | | 8-0 | 33-16-11 | D06156J | | 1 | | TB0018X | B001 | BJ | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0150
Page 6
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0152 | 286T0152 | | | P6-5-R2-MN PWR DISTR PNL (continued) | | | | | | | | | | | | | |
| 011 | 22 | | PA | 8-0 | 33-16-12 | D06156J | | 4 | | | | | TB0018Y | A018 | BJ | | ALL |
| 013 | 22 | | PA | 8-0 | 33-16-12 | TB0018Y | A018 | BJ | | | | | D06172J | 2 | | | ALL |
| 014 | 22 | | PA | 8-0 | 33-16-12 | TB0018Y | A018 | BJ | | | | | D06172J | 3 | | | ALL |
| 017 | 22 | | PA | 3-0 | 33-16-12 | D10288 | | A1 | | | | | TB0018Y | C018 | BJ | | ALL |
| 018 | 22 | | PA | 8-0 | 33-16-12 | D06172J | | 5 | | | | | TB0018Y | C018 | BJ | | ALL |
| 019 | 22 | | PA | 8-0 | 33-16-12 | D06172J | | 6 | | | | | TB0018Y | C018 | BJ | | ALL |
| 020 | 22 | | PA | 7-0 | 33-16-12 | D06172J | | 7 | | | | | D10288 | C1 | | | ALL |
| 021 | 20 | | PA | 2-0 | 33-16-12 | GD02420 | | D.. | 2 | | | | D10288 | A2 | | | ALL |
| 022 | 20 | | PA | 2-0 | 33-16-12 | GD02420 | | D.. | 2 | | | | D10288 | B2 | | | ALL |
| 023 | 20 | | PA | 2-0 | 33-16-12 | GD02420 | | D.. | 2 | | | | D10288 | C2 | | | ALL |
| 024 | 22 | | PA | 4-0 | 33-16-17 | D06172J | | 17 | | | | | D06156J | 11 | | | ALL |
| 026 | 22 | | PA | 8-0 | 33-16-17 | D06156J | | 19 | | | | | D10288 | D1 | | | ALL |
| 027 | 22 | | PA | 8-0 | 33-16-17 | D06156J | | 12 | | | | | D10288 | D2 | | | ALL |
| 028 | 22 | | PA | 3-0 | 33-16-21 | TB0018Y | A003 | BJ | | | | | D10294 | X1 | | | ALL |
| 029 | 22 | | PA | 3-0 | 33-16-21 | TB0018Y | C007 | BJ | | | | | D10294 | X2 | | | ALL |
| 030 | 20 | | PA | 2-0 | 33-16-21 | GD02418 | | D.. | 2 | | | | D10280 | A2 | | | ALL |
| 031 | 22 | | PA | 7-0 | 33-16-21 | D06172J | | 20 | | | | | D10280 | A1 | | | ALL |
| 032 | 22 | | PA | 3-0 | 33-16-21 | TB0018Y | C008 | BJ | | | | | D10280 | X2 | | | ALL |
| 033 | 22 | | PA | 3-0 | 33-16-21 | TB0018Y | A007 | BJ | | | | | D10280 | X1 | | | ALL |
| 034 | 22 | | PA | 6-0 | 33-16-22 | D06172J | | 10 | | | | | C00119 | 1 | D | *1 | ALL |
| 035 | 22 | | PQ | 6-0 | 33-16-22 | D06156J | | 13 | | | | | C00119 | 2 | D | | ALL |
| 035Z | | | C | 0-0 | 33-16-22 | D06156J | | DED | | | | | C00119 | DED | | | ALL |
| 036 | 22 | | PA | 6-0 | 33-16-22 | D06156J | | 14 | | | | | C00119 | 1 | D | *1 | ALL |
| 037 | 22 | | PA | 8-0 | 33-16-22 | D06156J | | 15 | | | | | D10294 | A1 | | | ALL |
| 038 | 22 | | PA | 8-0 | 33-16-22 | D06156J | | 16 | | | | | D10294 | B1 | | | ALL |
| 040 | 20 | | PA | 2-0 | 33-16-22 | GD02420 | | D.. | 2 | | | | D10294 | A2 | | | ALL |
| 041 | 20 | | PA | 2-0 | 33-16-22 | GD02420 | | D.. | 2 | | | | D10294 | B2 | | | ALL |
| 043 | 24 | | PK | 8-0 | 80-11-21 | D06156J | | 21 | | | | | TB0022D | A014 | 2 | | ALL |
| 044 | 24 | | PK | 2-0 | 80-11-21 | TB0022D | A002 | 2 | | | | | TB0022D | A014 | 2 | | ALL |
| 045 | 22 | | PA | 8-0 | 33-16-12 | D10288 | | B1 | | | | | D06156J | 5 | | | ALL |
| 046 | 24 | | PV | 8-0 | 80-11-11 | D06156J | | 30 | | | | | TB0018X | C001 | BJ | | ALL |
| 046Z | | | A | 0-0 | 80-11-11 | D06156J | | DED | | | | | TB0018X | DED | | | ALL |
| 047 | 24 | | PV | 8-0 | 80-11-21 | D06156J | | 31 | | | | | TB0018X | D001 | BJ | | ALL |
| 047Z | | | B | 0-0 | 80-11-21 | D06156J | | DED | | | | | TB0018X | DED | | | ALL |
| 048 | 22 | | PA | 8-0 | 33-16-21 | D06156J | | 7 | | | | | TB0018Y | C008 | BJ | | ALL |
| 059 | 22 | | PA | 6-0 | 34-12-62 | C01191 | | 2 | D | | | | D06172J | 8 | | | ALL |
| W0153 | 286T0153 | | | E2-2 C,SHELF | | | | | | | | | | | | | |
| 201B | 24 | | PW | 4-5 | 34-61-12 | D05151P | | 7 | | | | | TB0133G | 162 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0150

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0153 | 286T0153 | | | E2-2 C,SHELF (continued) | | | | | | | | | | | | | |
| 201R | 24 | PW | IA | 0-0 | 34-61-12 | D05151P | | 6 | | | | | TB0133G | 161 | 2 | | ALL |
| 201Z | | | IA | 0-0 | 34-61-12 | D05151P | | 8 | | | | | GDY0010 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 201Z | | | IA | 0-0 | 34-61-12 | D05151P | | 8 | | | | | GDY0011 | S.. | 2 | | 150-154 |
| 202B | 24 | PW | IB | 2-10 | 34-61-22 | D05723J | | 13 | | | | | TB0133G | 162 | 2 | | ALL |
| 202R | 24 | PW | IB | 0-0 | 34-61-22 | D05723J | | 12 | | | | | TB0133G | 161 | 2 | | ALL |
| 202Z | | | IB | 0-0 | 34-61-22 | D05723J | | 14 | | | | | GDY0010 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 202Z | | | IB | 0-0 | 34-61-22 | D05723J | | 14 | | | | | GDY0011 | S.. | 2 | | 150-154 |
| 205B | 24 | PW | IE | 2-10 | 31-35-13 | D05723J | | 8 | | | | | TB0133X | D051 | BJ | | ALL |
| 205R | 24 | PW | IE | 0-0 | 31-35-13 | D05723J | | 7 | | | | | TB0133X | C051 | BJ | | ALL |
| 205Z | | | IE | 0-0 | 31-35-13 | D05723J | | 9 | | | | | GDY0008 | S.. | 2 | | ALL |
| 207B | 24 | PW | IG | 4-4 | 31-35-13 | D05151P | | 14 | | | | | TB0133X | D052 | BJ | | ALL |
| 207R | 24 | PW | IG | 0-0 | 31-35-13 | D05151P | | 15 | | | | | TB0133X | C052 | BJ | | ALL |
| 207Z | | | IG | 0-0 | 31-35-13 | D05151P | | 18 | | | | | GDY0009 | S.. | 2 | | 050-099, 155-199, 275-299 |
| 207Z | | | IG | 0-0 | 31-35-13 | D05151P | | 18 | | | | | GDY0008 | S.. | 2 | | 150-154 |
| W0154 | 286T0154 | | | P6-5-R2-MN PWR DISTR PNL | | | | | | | | | | | | | |
| 002 | 22 | PA | | 6-0 | 33-16-12 | D06158J | | 4 | | | | | C00106 | 2 | D | | *1 ALL |
| 003 | 22 | PA | | 6-0 | 33-16-12 | D06174J | | 1 | | | | | C00106 | 2 | D | | *1 ALL |
| 004 | 22 | PA | | 7-0 | 33-16-12 | TB0018Y | | | C016 | BJ | | | C00106 | 1 | D | | ALL |
| 005 | 22 | PA | | 6-0 | 33-16-12 | D06158J | | 5 | | | | | C00108 | 2 | D | | ALL |
| 006 | 22 | PA | | 7-0 | 33-16-12 | D06174J | | 2 | | | | | TB0018X | B002 | BJ | | ALL |
| 007 | 22 | PA | | 8-0 | 33-16-12 | D06174J | | 3 | | | | | TB0018Y | C016 | BJ | | ALL |
| 008 | 22 | PQ | A | 6-0 | 33-16-12 | D06174J | | 4 | | | | | C00107 | 2 | D | | *1 ALL |
| 008Z | | | A | 0-0 | 33-16-12 | D06174J | | | DED | | | | C00107 | DED | | | ALL |
| 009 | 22 | PQ | B | 8-0 | 33-16-12 | D06174J | | 5 | | | | | TB0018Y | A017 | BJ | | ALL |
| 009Z | | | B | 0-0 | 33-16-12 | D06174J | | | DED | | | | TB0018Y | DED | | | ALL |
| 010 | 22 | PQ | C | 8-0 | 33-16-12 | D06174J | | 6 | | | | | TB0018Y | A017 | BJ | | ALL |
| 010Z | | | C | 0-0 | 33-16-12 | D06174J | | | DED | | | | TB0018Y | DED | | | ALL |
| 011 | 22 | PQ | D | 8-0 | 33-16-12 | C00107 | | 2 | | D | | *1 | TB0018Y | A017 | BJ | | ALL |
| 011Z | | | D | 0-0 | 33-16-12 | C00107 | | | DED | | | | TB0018Y | DED | | | ALL |
| 012 | 22 | PQ | E | 8-0 | 33-16-12 | C00107 | | 1 | | D | | | D06174J | 7 | | | 050-099, 155-199 |
| 012 | 22 | PQ | E | 8-0 | 33-16-12 | C00107 | | 1 | | D | | | TB0018Y | C017 | BJ | | 150-154, 275-278 |
| 012 | 22 | PQ | E | 6-0 | 33-16-12 | C00107 | | 1 | | D | | | D06174J | 7 | | | 280-299 |
| 012Z | | | E | 0-0 | 33-16-12 | C00107 | | | DED | | | | D06174J | DED | | | 050-099, 155-199, 280-299 |
| 012Z | | | E | 0-0 | 33-16-12 | C00107 | | | DED | | | | TB0018Y | DED | | | 150-154, 275-278 |

WIRE LIST
D280T132

91-21-11
Section W0150
Page 8
Mar 14/2007



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0154 | 286T0154 | | | P6-5-R2-MN PWR DISTR PNL (continued) | | | | | | | | | | | |
| 013 | 22 | PQ | F | | 8-0 | 33-16-12 | D06174J | | | | TB0018Y | C017 | BJ | | 150-154, 275-278 |
| 013Z | | | F | | 0-0 | 33-16-12 | D06174J | | DED | | TB0018Y | DED | | | 150-154, 275-278 |
| 014 | 22 | PQ | G | | 8-0 | 33-16-12 | D06174J | | | 8 | TB0018Y | C017 | BJ | | 150-154, 275-278 |
| 014Z | | | G | | 0-0 | 33-16-12 | D06174J | | DED | | TB0018Y | DED | | | 150-154, 275-278 |
| 015 | 22 | PA | | | 6-0 | 33-16-22 | D06174J | | | 10 | C00120 | 1 | D | *1 | ALL |
| 016 | 22 | PQ | K | | 6-0 | 33-16-22 | D06158J | | | 13 | C00120 | 2 | D | | ALL |
| 016Z | | | K | | 0-0 | 33-16-22 | D06158J | | DED | | C00120 | DED | | | ALL |
| 017 | 22 | PA | | | 6-0 | 33-16-22 | D06158J | | | 14 | C00120 | 1 | D | *1 | ALL |
| 018 | 22 | PQ | N | | 7-0 | 33-16-12 | D06158J | | | 6 | TB0018Y | A017 | BJ | | ALL |
| 018Z | | | N | | 0-0 | 33-16-12 | D06158J | | DED | | TB0018Y | DED | | | ALL |
| W0155 | 286T0155 | | | E2-3 C,SHELF | | | | | | | | | | | |
| 016 | 24 | PK | | | 5-0 | 31-31-26 | D04343P | | | 18 | TB0145X | B105 | BJ | | 050-099, 275-276 |
| 016 | 24 | PK | | | 6-0 | 31-31-26 | D04343P | | | 18 | TB0145X | B105 | BJ | | 150-199 |
| 016 | 24 | PK | | | 5-0 | 31-31-26 | D04343P | | | 18 | TB0145X | B111 | BJ | | 277-299 |
| 017 | 24 | PK | | | 5-0 | 31-31-26 | D04343P | | | 17 | TB0145X | B107 | BJ | | 050-099, 275-276 |
| 017 | 24 | PK | | | 6-0 | 31-31-26 | D04343P | | | 17 | TB0145X | B107 | BJ | | 150-199 |
| 017 | 24 | PK | | | 5-0 | 31-31-26 | D04343P | | | 17 | TB0145X | B113 | BJ | | 277-299 |
| 018 | 22 | PA | | | 6-0 | 31-31-22 | D04343P | | | 16 | TB0145Z | 166 | BJ | | 050-099, 275-299 |
| 018 | 22 | PA | | | 7-0 | 31-31-22 | D04343P | | | 16 | TB0145Z | 166 | BJ | | 150-199 |
| 201B | 24 | PW | IA | | 4-0 | 34-61-22 | D05723P | | | 13 | TB0145X | B152 | BJ | | ALL |
| 201R | 24 | PW | IA | | 0-0 | 34-61-22 | D05723P | | | 12 | TB0145X | A152 | BJ | | ALL |
| 201Z | | | IA | | 0-0 | 34-61-22 | D05723P | | | 14 | GDY0010 | S.. | 2 | | 050-099, 150-199, 275-276 |
| 201Z | | | IA | | 0-0 | 34-61-22 | D05723P | | | 14 | GDY0009 | S.. | 2 | | 277-299 |
| 207B | 24 | PW | IG | | 5-0 | 31-31-20 | D04343P | | | 4 | TB0145Y | C011 | BJ | | 050-099, 275-276 |
| 207B | 24 | PW | IG | | 6-0 | 31-31-20 | D04343P | | | 4 | TB0145Y | C011 | BJ | | 150-199 |
| 207B | 24 | PW | IG | | 5-0 | 31-31-20 | D04343P | | | 4 | TB0145Y | C017 | BJ | | 277-299 |
| 207R | 24 | PW | IG | | 0-0 | 31-31-20 | D04343P | | | 3 | TB0145Y | A011 | BJ | | 050-099, 150-199, 275-276 |
| 207R | 24 | PW | IG | | 0-0 | 31-31-20 | D04343P | | | 3 | TB0145Y | A017 | BJ | | 277-299 |
| 207Z | | | IG | | 0-0 | 31-31-20 | D04343P | | | 5 | GDY0002 | S.. | 2 | | ALL |
| 208B | 24 | PW | IH | | 5-0 | 31-31-20 | D04343P | | | 8 | TB0145Y | C012 | BJ | | 050-099, 275-276 |
| 208B | 24 | PW | IH | | 6-0 | 31-31-20 | D04343P | | | 8 | TB0145Y | C012 | BJ | | 150-199 |
| 208B | 24 | PW | IH | | 5-0 | 31-31-20 | D04343P | | | 8 | TB0145Y | C018 | BJ | | 277-299 |
| 208R | 24 | PW | IH | | 0-0 | 31-31-20 | D04343P | | | 7 | TB0145Y | A012 | BJ | | 050-099, 150-199, 275-276 |
| 208R | 24 | PW | IH | | 0-0 | 31-31-20 | D04343P | | | 7 | TB0145Y | A018 | BJ | | 277-299 |
| 208Z | | | IH | | 0-0 | 31-31-20 | D04343P | | | 9 | GDY0002 | S.. | 2 | | ALL |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0155 | 286T0155 | | | | E2-3 C,SHELF (continued) | | | | | | | | | | | | |
| 209B | 24 | PW | II | 5-0 | 31-31-20 | D04343P | | 12 | | | TB0145Y | C103 | BJ | | | | 050-099, 150-199, 275-276 |
| 209B | 24 | PW | II | 5-0 | 31-31-20 | D04343P | | 12 | | | TB0145Y | C109 | BJ | | | | 277-299 |
| 209R | 24 | PW | II | 0-0 | 31-31-20 | D04343P | | 11 | | | TB0145Y | A103 | BJ | | | | 050-099, 150-199, 275-276 |
| 209R | 24 | PW | II | 0-0 | 31-31-20 | D04343P | | 11 | | | TB0145Y | A109 | BJ | | | | 277-299 |
| 209Z | | | II | 0-0 | 31-31-20 | D04343P | | 10 | | | GDY0001 | S.. | 2 | | | | ALL |
| 210B | 24 | PW | IJ | 4-0 | 31-35-13 | D05723P | | 8 | | | TB0145Y | C135 | BJ | | | | ALL |
| 210R | 24 | PW | IJ | 0-0 | 31-35-13 | D05723P | | 7 | | | TB0145Y | A135 | BJ | | | | ALL |
| 210Z | | | IJ | 0-0 | 31-35-13 | D05723P | | 9 | | | GDY0006 | S.. | 2 | | | | ALL |
| 211 | 20 | UA | | 1-6 | 31-41-35 | GDY0012 | | S.. | 2 | | TB0145X | REF | | IK | | | 050-099, 150-199, 275-276 |
| 211B | 24 | PW | IK | 7-0 | 31-41-35 | D04343P | | 20 | | | TB0145X | D068 | BJ | | | | ALL |
| 211R | 24 | PW | IK | 0-0 | 31-41-35 | D04343P | | 19 | | | TB0145X | C068 | BJ | | | | ALL |
| 211Z | | | IK | 0-0 | 31-41-35 | TB0145X | | REF | | IK | D04343P | 21 | | | | | 050-099, 150-199, 275-276 |
| 211Z | | | IK | 0-0 | 31-41-35 | D04343P | | 21 | | | GDY0011 | S.. | 2 | | | | 277-299 |
| 212 | 20 | UA | | 1-6 | 28-41-11 | TB0145X | | REF | | IL | GDY0012 | S.. | 2 | | | | 050-099, 150-199, 275-276 |
| 212B | 24 | PW | IL | 7-0 | 28-41-11 | TB0145X | | B068 | BJ | | D04343P | 23 | | | | | ALL |
| 212R | 24 | PW | IL | 0-0 | 28-41-11 | TB0145X | | A068 | BJ | | D04343P | 22 | | | | | ALL |
| 212Z | | | IL | 0-0 | 28-41-11 | TB0145X | | REF | | IL | D04343P | 24 | | | | | 050-099, 150-199, 275-276 |
| 212Z | | | IL | 0-0 | 28-41-11 | GDY0011 | | S.. | 2 | | D04343P | 24 | | | | | 277-299 |
| 213B | 24 | PW | IM | 7-0 | 31-31-22 | D04343P | | 14 | | | TB0145Y | A049 | BJ | | | | 050-099, 150-199, 275-276 |
| 213B | 24 | PW | IM | 7-0 | 31-31-22 | D04343P | | 14 | | | TB0145Y | A085 | BJ | | | | 277-299 |
| 213R | 24 | PW | IM | 0-0 | 31-31-22 | D04343P | | 13 | | | TB0145X | A048 | BJ | | | | 050-099, 150-199, 275-276 |
| 213R | 24 | PW | IM | 0-0 | 31-31-22 | D04343P | | 13 | | | TB0145X | A084 | BJ | | | | 277-299 |
| 213Z | | | IM | 0-0 | 31-31-22 | D04343P | | 15 | | | GDY0009 | S.. | 2 | | | | 050-099, 150-199, 275-276 |
| 213Z | | | IM | 0-0 | 31-31-22 | D04343P | | 15 | | | GDY0013 | S.. | 2 | | | | 277-299 |
| 301 | 20 | UA | | 1-6 | 31-31-25 | GDY0012 | | S.. | 2 | | TB0145F | REF | | MA | | | 050-099, 150-199, 275-276 |
| 301B | 18 | PS | MA | 7-0 | 31-31-25 | D04343P | | 26 | DK | | TB0145G | 69 | 2 | | | | ALL |
| 301R | 18 | PS | MA | 0-0 | 31-31-25 | D04343P | | 25 | DK | | TB0145F | A070 | 2 | | | | ALL |
| 301Y | 18 | PS | MA | 0-0 | 31-31-25 | D04343P | | 27 | DK | | TB0145F | C070 | 2 | | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0150
Page 10
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0155 | 286T0155 | | | E2-3 C,SHELF (continued) | | | | | | | | | | | | |
| 301Z | | | | MA | 0-0 | 31-31-25 | D04343P | | 28 | | | TB0145F | REF | | MA | 050-099, 150-199, 275-276 |
| 301Z | | | | MA | 0-0 | 31-31-25 | D04343P | | 28 | | | GDY0011 | S.. | 2 | | 277-299 |
| W0156 | 286T0156 | | | P6-5-S2-MN PWR DISTR PNL | | | | | | | | | | | | |
| 001 | 24 | | PK | | 1-9 | 33-11-11 | TB0018Y | A004 | BJ | | | D10300 | X1 | | | ALL |
| 002 | 24 | | PK | | 1-10 | 33-11-11 | TB0018Y | A005 | BJ | | | D10300 | A1 | | | ALL |
| 004 | 24 | | PK | | 7-5 | 33-11-11 | TB0018Y | C003 | BJ | | | D06160J | 1 | | | ALL |
| 005 | 24 | | PK | | 6-7 | 33-11-11 | TB0018Y | A005 | BJ | | | D06168J | 1 | | | ALL |
| 006 | 24 | | PK | | 1-9 | 33-11-11 | TB0018Y | C003 | BJ | | | D10300 | A2 | | | ALL |
| 007 | 24 | | PK | | 2-7 | 33-11-11 | TB0018Y | A005 | BJ | | | D10306 | A1 | | | ALL |
| 008 | 24 | | PK | | 7-0 | 33-11-11 | D06168J | | 2 | | | TB0022Y | C018 | BJ | | ALL |
| 009 | 20 | | PA | | 1-7 | 33-11-11 | D10300 | | X2 | | | GD02418 | A.. | 2 | | ALL |
| 017 | 20 | | PA | | 2-6 | 33-11-14 | TB0018Y | C005 | BJ | | | D10310 | A1 | | | ALL |
| 018 | 16 | | PA | | 6-4 | 33-11-14 | D06160J | | 3 | FL | | D10310 | A3 | | | ALL |
| 021 | 16 | | PA | | 6-4 | 33-11-14 | D06160J | | 4 | FL | | D10310 | A2 | | | ALL |
| 022 | 24 | | PK | | 7-6 | 33-11-15 | D06160J | | 5 | | | TB0018Y | A006 | BJ | | ALL |
| 023 | 24 | | PK | | 2-6 | 33-11-15 | D10310 | | X1 | | | TB0018Y | A006 | BJ | | ALL |
| 024 | 20 | | PA | | 1-11 | 33-11-15 | D10310 | | X2 | | | GD02422 | A.. | 2 | | ALL |
| 025 | 24 | | PK | | 2-7 | 33-11-15 | D10306 | | X1 | | | TB0018Y | A006 | BJ | | ALL |
| 026 | 20 | | PA | | 1-11 | 33-11-15 | D10306 | | X2 | | | GD02422 | A.. | 2 | | ALL |
| 027 | 24 | | PK | | 7-7 | 33-16-11 | D06160J | | 6 | | | TB0018Z | 9 | BJ | | ALL |
| 028 | 24 | | PK | | 7-7 | 33-16-11 | D06160J | | 7 | | | TB0018Z | 10 | BJ | | ALL |
| 029 | 24 | | PK | | 1-9 | 33-16-11 | D10290 | | X1 | | | TB0018Z | 9 | BJ | | ALL |
| 030 | 24 | | PK | | 1-9 | 33-16-11 | D10290 | | X2 | | | TB0018Z | 10 | BJ | | ALL |
| 031 | 24 | | PK | | 6-8 | 33-16-11 | D06168J | | 15 | | | TB0018Z | 9 | BJ | | ALL |
| 032 | 24 | | PK | | 6-0 | 33-16-11 | D06168J | | 16 | | | D10510 | X2 | | | ALL |
| 033 | 24 | | PK | | 2-0 | 33-16-11 | D10270 | | A2 | | | TB0018Y | C006 | BJ | | ALL |
| 034 | 24 | | PK | | 2-2 | 33-16-11 | D10270 | | A1 | | | TB0018Z | 12 | BJ | | ALL |
| 035 | 24 | | PK | | 2-2 | 33-16-11 | D10270 | | X1 | | | TB0018Z | 12 | BJ | | ALL |
| 036 | 22 | | PA | | 2-8 | 33-16-11 | D10270 | | X2 | | | D10310 | D3 | | | ALL |
| 037 | 22 | | PA | | 2-5 | 33-16-11 | TB0018X | C002 | BJ | | | D10310 | D2 | | | ALL |
| 038 | 24 | | PK | | 6-8 | 33-16-11 | D06168J | | 30 | | | D10282 | A1 | | | ALL |
| 039 | 24 | | PK | | 6-8 | 33-16-11 | D06168J | | 31 | | | D10282 | B1 | | | ALL |
| 040 | 20 | | PA | | 1-9 | 33-16-11 | GD02418 | | D.. | 2 | | D10282 | A2 | | | ALL |
| 042 | 24 | | PK | | 1-11 | 33-16-11 | TB0018Y | C006 | BJ | | | D10282 | X1 | | | ALL |
| 043 | 24 | | PK | | 2-1 | 33-16-11 | TB0018Z | | 11 | BJ | | D10282 | X2 | | | ALL |
| 044 | 22 | | PA | | 7-10 | 33-16-12 | D06160J | | 8 | | | TB0018Y | C019 | BJ | | ALL |
| 045 | 22 | | PA | | 7-1 | 33-16-12 | C00109 | | 2 | D | *1 | TB0018Y | C019 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0150

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|---------|---------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0156 | 286T0156 | | | P6-5-S2-MN PWR DISTR PNL (continued) | | | | | | | | | | | |
| 046 | 22 | | PA | | 5-3 | 33-16-12 | C00109 | | 2 | D | *1 | D06168J | 21 | | ALL |
| 047 | 22 | | PA | | 6-11 | 33-16-12 | TB0018Y | | C019 | BJ | | D06168J | 22 | | ALL |
| 048 | 22 | | PA | | 7-1 | 33-16-12 | TB0018Y | | A020 | BJ | | C00109 | 1 | D | ALL |
| 049 | 22 | | PA | | 6-11 | 33-16-12 | TB0018Y | | A020 | BJ | | D06168J | 23 | | ALL |
| 050 | 22 | | PA | | 6-11 | 33-16-12 | TB0018Y | | A020 | BJ | | D06168J | 24 | | ALL |
| 051 | 22 | | PA | | 6-11 | 33-16-12 | TB0018Y | | C020 | BJ | | D06168J | 25 | | ALL |
| 052 | 22 | | PA | | 6-11 | 33-16-12 | TB0018Y | | C020 | BJ | | D06168J | 26 | | ALL |
| 053 | 22 | | PA | | 2-0 | 33-16-12 | TB0018Y | | C020 | BJ | | D10290 | A1 | | ALL |
| 054 | 22 | | PA | | 7-0 | 33-16-12 | TB0018Y | | A021 | BJ | | D06168J | 27 | | ALL |
| 055 | 22 | | PA | | 7-11 | 33-16-12 | TB0018Y | | A021 | BJ | | D06160J | 9 | | ALL |
| 056 | 22 | | PA | | 2-1 | 33-16-12 | TB0018Y | | A021 | BJ | | D10290 | B1 | | ALL |
| 057 | 22 | | PA | | 7-0 | 33-16-12 | TB0018Y | | C021 | BJ | | D06168J | 28 | | ALL |
| 058 | 22 | | PA | | 7-11 | 33-16-12 | TB0018Y | | C021 | BJ | | D06160J | 10 | | ALL |
| 059 | 22 | | PA | | 2-1 | 33-16-12 | TB0018Y | | C021 | BJ | | D10290 | C1 | | ALL |
| 060 | 20 | | PA | | 1-4 | 33-16-12 | GD02420 | | D.. | 2 | | D10290 | A2 | | ALL |
| 061 | 20 | | PA | | 1-4 | 33-16-12 | GD02420 | | D.. | 2 | | D10290 | B2 | | ALL |
| 062 | 20 | | PA | | 1-4 | 33-16-12 | GD02420 | | D.. | 2 | | D10290 | C2 | | ALL |
| 063 | 22 | | PA | | 3-1 | 33-16-17 | D06168J | | | 17 | | D06160J | 11 | | ALL |
| 065 | 22 | | PQ | E | 7-2 | 33-16-17 | D06160J | | | 19 | | D10290 | D1 | | ALL |
| 065Z | | | | E | 0-0 | 33-16-17 | D06160J | | | DED | | D10290 | DED | | ALL |
| 066 | 22 | | PQ | F | 7-2 | 33-16-17 | D06160J | | | 12 | | D10290 | D2 | | ALL |
| 066Z | | | | F | 0-0 | 33-16-17 | D06160J | | | DED | | D10290 | DED | | ALL |
| 067 | 22 | | PA | | 1-7 | 33-16-21 | D10296 | | | X1 | | TB0018Y | A003 | BJ | ALL |
| 068 | 22 | | PA | | 1-9 | 33-16-21 | D10296 | | | X2 | | TB0018Y | C007 | BJ | ALL |
| 069 | 22 | | PA | | 6-8 | 33-16-22 | D10298 | | | X1 | | C00125 | 2 | D | *1 |
| 070 | 20 | | PA | | 1-9 | 33-16-22 | D10298 | | | X2 | | GD02418 | D.. | 2 | ALL |
| 071 | 22 | | PA | | 2-2 | 33-16-21 | D10270 | | | B1 | | TB0018Z | 12 | BJ | ALL |
| 072 | 22 | | PA | | 2-1 | 33-16-21 | D10270 | | | B2 | | TB0018Y | A007 | BJ | ALL |
| 073 | 22 | | PA | | 1-11 | 33-16-21 | D10284 | | | X2 | | TB0018Y | C008 | BJ | ALL |
| 074 | 22 | | PA | | 1-11 | 33-16-21 | D10284 | | | X1 | | TB0018Y | A007 | BJ | ALL |
| 075 | 20 | | PA | | 1-8 | 33-16-21 | D10284 | | | A2 | | GD02418 | D.. | 2 | ALL |
| 076 | 22 | | PA | | 6-7 | 33-16-21 | D10284 | | | A1 | | D06168J | 20 | | ALL |
| 077 | 22 | | PQ | D | 5-3 | 33-16-22 | C00122 | | | 1 | D | *1 | D06168J | 10 | ALL |
| 077Z | | | | D | 0-0 | 33-16-22 | C00122 | | | DED | | D06168J | DED | | ALL |
| 078 | 22 | | PA | | 5-3 | 33-16-22 | C00125 | | | 2 | D | *1 | D06168J | 11 | ALL |
| 079 | 22 | | PA | | 6-7 | 33-16-22 | D10298 | | | A1 | | D06168J | 12 | | ALL |
| 080 | 22 | | PQ | C | 6-7 | 33-16-22 | C00122 | | | 1 | D | *1 | D06160J | 13 | ALL |
| 080Z | | | | C | 0-0 | 33-16-22 | C00122 | | | DED | | D06160J | DED | | ALL |
| 081 | 22 | | PA | | 6-7 | 33-16-22 | C00122 | | | 2 | D | *2 | D06160J | 14 | ALL |

WIRE LIST
D280T132

91-21-11
Section W0150
Page 12
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|---------|-------------|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0156 | 286T0156 | | | P6-5-S2-MN PWR DISTR PNL (continued) | | | | | | | | | | | | | |
| 082 | 22 | | PA | 6-5 | 33-16-22 | C00122 | | 2 | D | | * | | | D10296 | C1 | | ALL |
| 083 | 22 | | PA | 6-7 | 33-16-22 | C00125 | | 1 | D | | | | | D06160J | 15 | | ALL |
| 084 | 22 | | PA | 1-7 | 33-16-22 | D10298 | | A2 | | | | | | D10296 | C3 | | ALL |
| 085 | 22 | | PA | 7-3 | 33-16-22 | D06160J | | 16 | | | | | | D10296 | C2 | | ALL |
| 086 | 22 | | PA | 7-3 | 33-16-22 | D10296 | | B1 | | | | | | D06160J | 17 | | ALL |
| 087 | 22 | | PA | 7-3 | 33-16-22 | D10296 | | A1 | | | | | | D06160J | 18 | | ALL |
| 088 | 20 | | PA | 1-4 | 33-16-22 | D10296 | | B2 | | | | | | GD02420 | D.. 2 | | ALL |
| 089 | 20 | | PA | 1-4 | 33-16-22 | D10296 | | A2 | | | | | | GD02420 | D.. 2 | | ALL |
| 090 | 24 | | PK | 7-10 | 80-11-21 | M10335 | | B | C | | * | | | D06160J | 32 | | ALL |
| 091 | 24 | | PK | 1-11 | 80-11-21 | M10335 | | B | C | | * | | | D10264 | D2 | | ALL |
| 092 | 24 | | PK | 7-10 | 80-11-21 | TB0022Y | | C015 | BJ | | | | | D06160J | 33 | | ALL |
| 093 | 24 | | PK | 1-8 | 80-11-21 | D10264 | | D3 | | | | | | TB0022Y | C005 BJ | | ALL |
| 094 | 24 | | PK | 7-2 | 80-11-21 | D10264 | | D1 | | | | | | D06160J | 34 | | ALL |
| 095 | 24 | | PK | 1-8 | 80-11-21 | D10264 | | C3 | | | | | | TB0022Y | C005 BJ | | ALL |
| 096 | 24 | | PK | 7-7 | 80-11-21 | D06160J | | 35 | | | | | | TB0022Y | C005 BJ | | ALL |
| 097 | 24 | | PK | 7-2 | 80-11-21 | D06160J | | 36 | | | | | | D10264 | C1 | | ALL |
| 098 | 24 | | PK | 7-7 | 80-11-21 | D06160J | | 37 | | | | | | TB0022Y | C006 BJ | | ALL |
| 099 | 24 | | PK | 2-0 | 80-11-21 | D10264 | | C2 | | | | | | TB0022Y | C015 BJ | | ALL |
| 100 | 20 | | PA | 7-7 | 80-11-21 | D06160J | | 28 | | | | | | TB0022Y | A006 BJ | | ALL |
| 101 | 20 | | PA | 1-8 | 80-11-21 | D10264 | | B2 | | | | | | TB0022Y | A006 BJ | | ALL |
| 102 | 24 | | PK | 1-8 | 80-11-21 | D10264 | | X1 | | | | | | TB0022Y | A006 BJ | | ALL |
| 103 | 24 | | PK | 1-8 | 80-11-21 | D10264 | | X2 | | | | | | TB0022Y | C006 BJ | | ALL |
| 104 | 24 | | PK | 7-7 | 80-11-21 | D06160J | | 30 | | | | | | TB0022Y | C006 BJ | | ALL |
| 105 | 20 | | PA | 1-9 | 80-11-21 | D10264 | | B1 | | | | | | TB0022Y | A007 BJ | | ALL |
| 106 | 20 | | PA | 7-7 | 80-11-21 | D06160J | | 38 | | | | | | TB0022Y | A007 BJ | | ALL |
| 107 | 24 | | PK | 8-0 | 80-11-21 | D06160J | | 39 | | | | | | TB0022Z | 21 BJ | | ALL |
| 108 | 24 | | PK | 1-10 | 80-11-21 | D10268 | | D1 | | | | | | TB0022Y | A005 BJ | | ALL |
| 109 | 24 | | PK | 7-4 | 80-11-21 | D10268 | | B1 | | | | | | D06160J | 41 | | ALL |
| 110 | 20 | | PA | 8-0 | 80-11-21 | TB0022Z | | 21 | BJ | | | | | D06160J | 29 | | ALL |
| 111 | 20 | | PA | 8-0 | 80-11-21 | TB0022Z | | 21 | BJ | | | | | D06160J | 31 | | ALL |
| 112 | 24 | | PK | 2-3 | 80-11-21 | TB0022Z | | 21 | BJ | | | | | D10268 | B2 | | ALL |
| 113 | 24 | | PK | 1-11 | 80-11-21 | TB0022Y | | A007 | BJ | | | | | D10268 | X1 | | ALL |
| 114 | 20 | | PA | 1-7 | 80-11-21 | GD02422 | | D.. | 2 | | | | | D10268 | X2 | | ALL |
| 115 | 24 | | PK | 1-9 | 80-11-21 | TB0022Y | | C003 | BJ | | | | | D10268 | D2 | | ALL |
| 134 | 24 | | PK | 1-11 | 24-51-71 | D10268 | | A2 | | | | | | TB0022Y | A008 BJ | | ALL |
| 135 | 24 | | PK | 1-11 | 24-51-71 | D10268 | | A1 | | | | | | TB0022Y | C008 BJ | | ALL |
| 136 | 22 | | PA | 7-2 | 36-11-52 | D10264 | | A2 | | | | | | D06160J | 20 | | ALL |
| 137 | 20 | | PA | 1-6 | 36-11-52 | D10264 | | A1 | | | | | | GD02422 | D.. 2 | | ALL |
| 138 | 24 | | PK | 1-6 | 80-11-21 | TB0022D | | C002 | 2 | | | | | TB0022Y | C015 BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0150

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|---------|---------|--------|-------------|-----|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0156 | 286T0156 | | | P6-5-S2-MN PWR DISTR PNL (continued) | | | | | | | | | | | | |
| 141 | 22 | | PA | | 7-10 | 33-16-12 | D06160J | | | | 48 | TB0018Y | C019 | BJ | ALL | |
| 142 | 22 | | PA | | 7-10 | 33-16-12 | D06160J | | | | 49 | TB0018Y | C020 | BJ | ALL | |
| 148 | 24 | | PK | | 1-8 | 80-11-21 | D10268 | | | | C1 | TB0018X | D001 | BJ | ALL | |
| 149 | 24 | | PK | | 2-3 | 80-11-21 | D10268 | | | | C2 | TB0022Z | 21 | BJ | ALL | |
| 150 | 24 | | PK | | 2-11 | 33-11-11 | D10306 | | | | A2 | TB0022Y | C018 | BJ | ALL | |
| 155 | 20 | | PA | | 2-11 | 33-11-13 | D10432 | | | | A3 | R00556 | = B | \$ | ALL | |
| 156 | 20 | | PA | | 6-7 | 33-11-13 | D10432 | | | | A2 | D06160J | 51 | | ALL | |
| 157 | 20 | | PA | | 6-7 | 33-11-13 | D10432 | | | | A1 | D06160J | 52 | | ALL | |
| 158 | 24 | | PK | | 6-7 | 33-11-13 | D10432 | | | | X1 | D06160J | 53 | | ALL | |
| 159 | 20 | | PA | | 2-1 | 33-11-13 | D10432 | | | | X2 | GD02418 | A.. | 2 | ALL | |
| 160 | 20 | | PA | | 8-1 | 33-11-13 | D06160J | | | | 50 | R00556 | = A | \$ | ALL | |
| 162 | 20 | | UA | | 1-11 | 33-11-11 | GD02422 | | | | S.. | 2 | D10306 | | FM | ALL |
| 163 | 20 | | UA | | 1-7 | 33-11-11 | D10300 | | | | | | GD02418 | S.. | 2 | ALL |
| 164 | 24 | | PK | | 2-2 | 33-11-11 | D10300 | | | | A3 | FL | TB0022Y | C018 | BJ | ALL |
| 165 | 24 | | PK | | 1-10 | 33-16-11 | D10510 | | | | A1 | | TB0018X | D002 | BJ | ALL |
| 166 | 24 | | PK | | 2-0 | 33-16-11 | D10510 | | | | X1 | | TB0018Z | 9 | BJ | ALL |
| 167 | 24 | | PK | | 2-0 | 33-16-11 | D10510 | | | | B1 | | D10282 | B2 | | ALL |
| 168 | 20 | | PA | | 1-4 | 33-16-11 | D10510 | | | | A2 | | GD02422 | D.. | 2 | ALL |
| 169 | 20 | | PA | | 1-4 | 33-16-11 | D10510 | | | | B2 | | GD02422 | D.. | 2 | ALL |
| 170 | 22 | | PA | | 1-3 | 33-16-21 | TB0018Z | | | | 9 | BJ | TB0018Y | A003 | BJ | ALL |
| 171 | 24 | | PK | | 1-11 | 80-11-21 | M10335 | | | | A | C | TB0022D | C014 | 2 | ALL |
| 174 | 16 | | PA | | 6-10 | 33-13-18 | D06168J | | | | 38 | FM | TB0018F | A013 | 2 | ALL |
| 175 | 24 | | PV | G | 6-7 | 49-72-11 | C00005 | | | | 2 | D | D06160J | 45 | | ALL |
| 175Z | | | | G | 0-0 | 49-72-11 | C00005 | | | | DED | | D06160J | DED | | ALL |
| 176 | 24 | | PV | H | 6-7 | 49-72-11 | C00005 | | | | 1 | D | D06160J | 46 | | ALL |
| 176Z | | | | H | 0-0 | 49-72-11 | C00005 | | | | DED | | D06160J | DED | | ALL |
| 187 | 22 | | PA | | 5-0 | 34-12-61 | C01190 | | | | 2 | D | D06168J | 9 | | ALL |
| 201B | 24 | | PW | A | 5-0 | 33-11-11 | D10306 | | | | B1 | | D06168J | 3 | | ALL |
| 201R | 24 | | PW | A | 0-0 | 33-11-11 | D10306 | | | | B2 | | D06168J | 4 | | ALL |
| 201Z | | | | A | 0-0 | 33-11-11 | D06168J | | | | | FA | D10306 | | FM | ALL |
| 301B | 24 | | PX | B | 6-6 | 33-11-11 | D10300 | | | | B1 | | D06168J | 5 | | ALL |
| 301R | 24 | | PX | B | 0-0 | 33-11-11 | D10300 | | | | B2 | | D06168J | 6 | | ALL |
| 301Y | 24 | | PX | B | 0-0 | 33-11-11 | D10300 | | | | B3 | | D06168J | 7 | | ALL |
| 301Z | | | | B | 0-0 | 33-11-11 | D06168J | | | | | FA | D10300 | | FL | ALL |
| FRA | | | | | 0-0 | 33-11-11 | D06168J | | | | | FA | D06168J | 8 | | ALL |
| PA2 | | | | | 0-0 | 99-99-99 | D10306 | | | | G1 | | D10306 | G3 | | ALL |
| PA3 | | | | | 0-0 | 99-99-99 | D10310 | | | | G1 | | D10310 | G3 | | ALL |
| PA4 | | | | | 0-0 | 99-99-99 | D10432 | | | | G1 | | D10432 | G3 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0150

Page 14

Mar 14/2007

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----|--------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0157 | 286T0157 | | | | FWD CABIN MID (L) | | | | | | | | | | | |
| 028 | 20 | | PA | | 5-0 | 33-27-11 | D06740P | | 8 | | | D13555 | | 5 | | 050-099, 150-154, 157-165, 167-199 |
| 028 | 20 | | PQ | BC | 5-0 | 33-27-11 | D06740P | | 8 | | | D13555 | | 5 | | 155-156, 166 |
| 028Z | | | | BC | 0-0 | 33-27-11 | D06740P | | DED | | | D13555 | | DED | | 155-156, 166 |
| 029 | 20 | | PA | | 5-0 | 33-27-11 | D06740P | | 1 | | | D13556 | | 5 | | 050-099, 150-154, 157-165, 167-199 |
| 029 | 20 | | PQ | BD | 5-0 | 33-27-11 | D06740P | | 1 | | | D13556 | | 5 | | 155-156, 166 |
| 029Z | | | | BD | 0-0 | 33-27-11 | D06740P | | DED | | | D13556 | | DED | | 155-156, 166 |
| 030 | 20 | | PA | | 5-0 | 33-27-11 | D06740P | | 2 | | | D13555 | | 7 | | 050-099, 150-154, 157-165, 167-199 |
| 030 | 20 | | PQ | BE | 5-0 | 33-27-11 | D06740P | | 2 | | | D13555 | | 7 | | 155-156, 166 |
| 030Z | | | | BE | 0-0 | 33-27-11 | D06740P | | DED | | | D13555 | | DED | | 155-156, 166 |
| 031 | 20 | | PA | | 5-0 | 33-27-11 | SP00457 | | | 9 | | D13555 | | 12 | | 050-099, 150-199 |
| 032 | 20 | | PA | | 5-0 | 33-27-11 | SP00459 | | | 9 | | D13555 | | 11 | | 050-099, 150-199 |
| 033 | 20 | | PA | | 5-0 | 33-27-11 | D06740P | | | 3 | | D13555 | | 8 | | 050-099, 150-199 |
| 034 | 20 | | PA | | 5-0 | 33-27-11 | D13555 | | 10 | | | SP00463 | | 9 | | 050-099, 150-199 |
| 035 | 20 | | PA | | 5-0 | 33-27-11 | D13555 | | 9 | | | SP00465 | | 9 | | 050-099, 150-199 |
| 036 | 20 | | PA | | 8-0 | 33-27-11 | D06740P | | 4 | | | L01106 | = G | E | * | 050-099 |
| 036 | 20 | | PA | | 7-0 | 33-27-11 | D06740P | | 4 | | | L01106 | = G | E | * | 150-199 |
| 044 | 20 | | PA | | 5-0 | 33-27-11 | D13556 | | 7 | | | D06740P | | 5 | | 050-099, 150-154, 157-165, 167-199 |
| 044 | 20 | | PQ | BS | 5-0 | 33-27-11 | D13556 | | 7 | | | D06740P | | 5 | | 155-156, 166 |
| 044Z | | | | BS | 0-0 | 33-27-11 | D13556 | | DED | | | D06740P | | DED | | 155-156, 166 |
| 045 | 20 | | PA | | 5-0 | 33-27-11 | SP00471 | | | 9 | | D13556 | | 12 | | 050-099, 150-199 |
| 046 | 20 | | PA | | 5-0 | 33-27-11 | SP00473 | | | 9 | | D13556 | | 11 | | 050-099, 150-199 |
| 050 | 20 | | PA | | 5-0 | 33-27-11 | SP00467 | | | 9 | | D13556 | | 9 | | 050-099, 150-199 |
| 051 | 20 | | PA | | 5-0 | 33-27-11 | SP00469 | | | 9 | | D13556 | | 10 | | 050-099, 150-199 |
| 052 | 20 | | PA | | 5-0 | 33-27-11 | D06740P | | 6 | | | D13556 | | 8 | | 050-099, 150-199 |
| 058 | 20 | | PA | | 8-0 | 33-27-11 | D06740P | | 7 | | | L01106 | = G | E | * | 050-099 |
| 058 | 20 | | PA | | 7-0 | 33-27-11 | D06740P | | 7 | | | L01106 | = G | E | * | 150-199 |
| A-B | | | | | 0-0 | 33-27-11 | SP00463 | | | 9 | | L01106 | | BLK | | 050-099, 150-199 |
| A-C | | | | | 0-0 | 33-27-11 | SP00465 | | | 9 | | L01106 | | BLK | | 050-099, 150-199 |
| A-D | | | | | 0-0 | 33-27-11 | SP00459 | | | 9 | | L01106 | | WHT | | 050-099, 150-199 |
| A-E | | | | | 0-0 | 33-27-11 | SP00457 | | | 9 | | L01106 | | WHT | | 050-099, 150-199 |
| A-G | | | | | 0-0 | 33-27-11 | SP00473 | | | 9 | | L01107 | | WHT | | 050-099, 150-199 |
| A-H | | | | | 0-0 | 33-27-11 | SP00471 | | | 9 | | L01107 | | WHT | | 050-099, 150-199 |
| A-I | | | | | 0-0 | 33-27-11 | SP00467 | | | 9 | | L01107 | | BLK | | 050-099, 150-199 |
| A-J | | | | | 0-0 | 33-27-11 | SP00469 | | | 9 | | L01107 | | BLK | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0150

Page 15

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0158 | 286T0158 | | | P6-5-S2-MN PWR DISTR PNL | | | | | | | | | | | |
| 002 | 24 | | PK | | 1-7 | 33-11-11 | D10302 | X1 | | | TB0018Y | A004 | BJ | | ALL |
| 003 | 24 | | PK | | 1-7 | 33-11-11 | D10302 | A1 | | | TB0018Y | C004 | BJ | | ALL |
| 004 | 24 | | PK | | 6-3 | 33-11-11 | TB0018Y | C004 | BJ | | D06170J | 1 | | | ALL |
| 005 | 24 | | PK | | 1-7 | 33-11-11 | D10302 | A2 | | | TB0018Y | C003 | BJ | | ALL |
| 006 | 24 | | PK | | 2-2 | 33-11-11 | TB0018Y | C004 | BJ | | D10308 | A1 | | | ALL |
| 007 | 24 | | PK | | 6-8 | 33-11-11 | D06170J | 2 | | | TB0022Y | A018 | BJ | | ALL |
| 008 | 20 | | PA | | 1-10 | 33-11-11 | D10302 | X2 | | | GD02422 | A.. | 2 | | ALL |
| 009 | 24 | | PK | | 2-2 | 33-11-15 | TB0018Y | A006 | BJ | | D10308 | X1 | | | ALL |
| 010 | 20 | | PA | | 2-1 | 33-11-15 | GD02418 | A.. | 2 | | D10308 | X2 | | | ALL |
| 011 | 22 | | PQ | H | 5-3 | 33-16-12 | D06162J | 8 | | | C00110 | 1 | D | *1 | ALL |
| 011Z | | | | H | 0-0 | 33-16-12 | D06162J | DED | | | C00110 | DED | | | ALL |
| 012 | 22 | | PA | | 4-10 | 33-16-12 | D06170J | 21 | | | C00110 | 2 | D | *2 | ALL |
| 013 | 22 | | PA | | 4-10 | 33-16-12 | D06170J | 22 | | | C00110 | 2 | D | *2 | ALL |
| 014 | 22 | | PQ | J | 4-10 | 33-16-12 | D06170J | 23 | | | C00110 | 1 | D | *1 | ALL |
| 014Z | | | | J | 0-0 | 33-16-12 | D06170J | DED | | | C00110 | DED | | | ALL |
| 015 | 22 | | PQ | C | 4-8 | 33-16-12 | D06170J | 24 | | | C00112 | 2 | D | | ALL |
| 015Z | | | | C | 0-0 | 33-16-12 | D06170J | DED | | | C00112 | DED | | | ALL |
| 016 | 22 | | PQ | D | 4-8 | 33-16-12 | D06170J | 25 | | | C00112 | 1 | D | | ALL |
| 016Z | | | | D | 0-0 | 33-16-12 | D06170J | DED | | | C00112 | DED | | | ALL |
| 017 | 22 | | PQ | E | 6-8 | 33-16-12 | D06170J | 26 | | | TB0018Y | A019 | BJ | | ALL |
| 017Z | | | | E | 0-0 | 33-16-12 | D06170J | DED | | | TB0018Y | DED | | | ALL |
| 018 | 22 | | PQ | F | 6-8 | 33-16-12 | D06170J | 27 | | | TB0018Y | A019 | BJ | | ALL |
| 018Z | | | | F | 0-0 | 33-16-12 | D06170J | DED | | | TB0018Y | DED | | | ALL |
| 021 | 22 | | PQ | G | 7-1 | 33-16-12 | TB0018Y | A019 | BJ | | D06162J | 9 | | | ALL |
| 021Z | | | | G | 0-0 | 33-16-12 | TB0018Y | DED | | | D06162J | DED | | | ALL |
| 022 | 22 | | PQ | K | 4-9 | 33-16-22 | D06170J | 10 | | | C00123 | 1 | D | * | ALL |
| 022Z | | | | K | 0-0 | 33-16-22 | D06170J | DED | | | C00123 | DED | | | ALL |
| 023 | 22 | | PA | | 5-2 | 33-16-22 | D06162J | 13 | | | C00123 | 2 | D | | ALL |
| 024 | 22 | | PQ | I | 5-2 | 33-16-22 | D06162J | 17 | | | C00123 | 1 | D | * | 050-099 |
| 024 | 22 | | PQ | M | 5-2 | 33-16-22 | D06162J | 17 | | | C00123 | 1 | D | * | 150-199, 275-299 |
| 024Z | | | | I | 0-0 | 33-16-22 | D06162J | DED | | | C00123 | DED | | | 050-099 |
| 024Z | | | | M | 0-0 | 33-16-22 | D06162J | DED | | | C00123 | DED | | | 150-199, 275-299 |
| 028 | 24 | | PK | | 7-2 | 80-11-11 | D06162J | 32 | | | M10334 | B | C | *1 | ALL |
| 029 | 24 | | PK | | 2-3 | 80-11-11 | D10262 | D2 | | | M10334 | B | C | *1 | ALL |
| 030 | 24 | | PK | | 7-0 | 80-11-11 | D06162J | 33 | | | TB0022Y | A015 | BJ | | ALL |
| 031 | 24 | | PK | | 2-2 | 80-11-11 | D10262 | D3 | | | TB0022Y | A020 | BJ | | ALL |
| 032 | 24 | | PK | | 7-0 | 80-11-11 | D10262 | D1 | | | D06162J | 34 | | | ALL |
| 033 | 24 | | PK | | 2-2 | 80-11-11 | D10262 | C3 | | | TB0022Y | A020 | BJ | | ALL |
| 034 | 24 | | PK | | 7-2 | 80-11-11 | D06162J | 35 | | | TB0022Y | A020 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0150
Page 16
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0158 | 286T0158 | | | P6-5-S2-MN PWR DISTR PNL (continued) | | | | | | | | | | | | | |
| 035 | 24 | | PK | 7-0 | 80-11-11 | D06162J | | 36 | | | | | D10262 | C1 | | | ALL |
| 036 | 24 | | PK | 6-9 | 80-11-11 | D06162J | | 37 | | | | | TB0022Y | A003 | BJ | | ALL |
| 037 | 24 | | PK | 2-1 | 80-11-11 | D10262 | | C2 | | | | | TB0022Y | A015 | BJ | | ALL |
| 038 | 20 | | PA | 7-2 | 80-11-11 | D06162J | | 28 | | | | | TB0022Y | C020 | BJ | | ALL |
| 039 | 20 | | PA | 2-2 | 80-11-11 | D10262 | | B2 | | | | | TB0022Y | C020 | BJ | | ALL |
| 040 | 24 | | PK | 2-2 | 80-11-11 | D10262 | | X1 | | | | | TB0022Y | C020 | BJ | | ALL |
| 041 | 24 | | PK | 1-9 | 80-11-11 | D10262 | | X2 | | | | | TB0022Y | A003 | BJ | | ALL |
| 042 | 24 | | PK | 6-9 | 80-11-11 | D06162J | | 30 | | | | | TB0022Y | A003 | BJ | | ALL |
| 043 | 20 | | PA | 1-9 | 80-11-11 | D10262 | | B1 | | | | | TB0022Y | A004 | BJ | | ALL |
| 044 | 20 | | PA | 6-9 | 80-11-11 | D06162J | | 38 | | | | | TB0022Y | A004 | BJ | | ALL |
| 045 | 24 | | PK | 7-2 | 80-11-11 | D06162J | | 39 | | | | | TB0022Z | 22 | BJ | | ALL |
| 046 | 22 | | PA | 6-9 | 80-11-11 | D06162J | | 40 | | | | | TB0022Y | A005 | BJ | | ALL |
| 047 | 24 | | PK | 1-9 | 80-11-11 | D10266 | | D1 | | | | | TB0022Y | A005 | BJ | | ALL |
| 048 | 24 | | PK | 6-11 | 80-11-11 | D10266 | | B1 | | | | | D06162J | 41 | | | ALL |
| 049 | 22 | | PA | 6-9 | 80-11-11 | TB0022Y | | C003 | BJ | | | | D06162J | 42 | | | ALL |
| 050 | 24 | | PK | 1-9 | 80-11-11 | TB0022Y | | A004 | BJ | | | | D10266 | X1 | | | ALL |
| 051 | 20 | | PA | 7-2 | 80-11-11 | TB0022Z | | 22 | BJ | | | | D06162J | 29 | | | ALL |
| 052 | 20 | | PA | 7-2 | 80-11-11 | TB0022Z | | 22 | BJ | | | | D06162J | 31 | | | ALL |
| 053 | 24 | | PK | 1-9 | 80-11-11 | TB0022Y | | C003 | BJ | | | | D10266 | D2 | | | ALL |
| 054 | 24 | | PK | 2-2 | 80-11-11 | TB0022Z | | 22 | BJ | | | | D10266 | B2 | | | ALL |
| 055 | 20 | | PA | 1-11 | 80-11-11 | GD02422 | | D.. | 2 | | | | D10266 | X2 | | | ALL |
| 076 | 24 | | PK | 1-10 | 24-51-71 | D10266 | | A2 | | | | | TB0022Y | A008 | BJ | | ALL |
| 077 | 24 | | PK | 1-10 | 24-51-71 | D10266 | | A1 | | | | | TB0022Y | C008 | BJ | | ALL |
| 078 | 22 | | PA | 7-0 | 36-11-51 | D10262 | | A2 | | | | | D06162J | 20 | | | ALL |
| 079 | 20 | | PA | 1-11 | 36-11-51 | D10262 | | A1 | | | | | GD02422 | D.. | 2 | | ALL |
| 080 | 24 | | PK | 1-7 | 80-11-11 | TB0022D | | C001 | 2 | | | | TB0022Y | A015 | BJ | | ALL |
| 083 | 24 | | PK | 1-7 | 80-11-11 | D10266 | | C1 | | | | | TB0018X | C001 | BJ | | ALL |
| 084 | 24 | | PK | 2-2 | 80-11-11 | D10266 | | C2 | | | | | TB0022Z | 22 | BJ | | ALL |
| 101 | 22 | | PA | 6-9 | 33-16-21 | D06162J | | 7 | | | | | TB0018Y | C007 | BJ | | ALL |
| 105 | 22 | | PQ | 6-8 | 33-16-12 | D06170J | | 28 | | | | | TB0018Y | A019 | BJ | | ALL |
| 105Z | | | T | 0-0 | 33-16-12 | D06170J | | DED | | | | | TB0018Y | DED | | | ALL |
| 110 | 24 | | PK | 2-7 | 33-11-11 | D10308 | | A2 | | | | | TB0022Y | A018 | BJ | | ALL |
| 114 | 20 | | UA | 1-8 | 33-11-11 | GD02422 | | S.. | 2 | | | | D10308 | | | FM | ALL |
| 115 | 20 | | UA | 1-7 | 33-11-11 | D10302 | | | | FL | | | GD02418 | S.. | 2 | | ALL |
| 116 | 24 | | PK | 2-1 | 33-11-11 | D10302 | | A3 | | | | | TB0022Y | A018 | BJ | | ALL |
| 117 | 24 | | PK | 2-1 | 80-11-11 | M10334 | | A | C | | | | TB0022D | C013 | 2 | | ALL |
| 201B | 24 | | PW | A | 4-11 | 33-11-11 | D06170J | 3 | | | | | D10308 | B1 | | | ALL |
| 201R | 24 | | PW | A | 0-0 | 33-11-11 | D06170J | 4 | | | | | D10308 | B2 | | | ALL |
| 201Z | | | A | 0-0 | 33-11-11 | D06170J | | | | FA | | | D10308 | | | FM | ALL |

WIRE LIST

D280T132

91-21-11

Section W0150

Page 17

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | To | | | | |
|--------------|-----------------|-------------|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0158 | 286T0158 | | | | P6-5-S2-MN PWR DISTR PNL (continued) | | | | | | | | | | |
| 301B | 24 | PX | B | | 6-6 | 33-11-11 | D06170J | | 5 | | D10302 | | B1 | | ALL |
| 301R | 24 | PX | B | | 0-0 | 33-11-11 | D06170J | | 6 | | D10302 | | B2 | | ALL |
| 301Y | 24 | PX | B | | 0-0 | 33-11-11 | D06170J | | 7 | | D10302 | | B3 | | ALL |
| 301Z | | | B | | 0-0 | 33-11-11 | D06170J | | | FA | D10302 | | | FL | ALL |
| FRA | | | | | 0-0 | 33-11-11 | D06170J | | | FA | D06170J | | 8 | | ALL |
| PA1 | | | | | 0-0 | 99-99-99 | D10308 | | G1 | | D10308 | | G3 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0150
Page 18 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0161 | 286T0161 | | | E1-6 L,SHELF | | | | | | | | | | | | |
| 003 | 22 | | PA | | 3-6 | 34-21-11 | D04699P | | 3 | | | | D00367B | D01 | | ALL |
| 004 | 22 | | PA | | 3-6 | 34-21-11 | D04699P | | 4 | | | | D00367B | D02 | | ALL |
| 005 | 22 | | PA | | 3-6 | 34-21-11 | D04699P | | 5 | | | | D00367B | D03 | | ALL |
| 006 | 24 | | PV | AF | 3-3 | 34-21-11 | D04201P | | 1 | | | | D00367C | 1 | | ALL |
| 006Z | | | | AF | 0-0 | 34-21-11 | D04201P | DED | | | | | D00367C | DED | | ALL |
| 007 | 20 | | PA | | 2-2 | 34-21-11 | GDX0003 | | A.. | 2 | | | D00367C | 5 | | ALL |
| 008 | 16 | | PA | | 2-2 | 34-21-11 | GDX0003 | | D.. | 2 | | | D00367C | 8 | | ALL |
| 009 | 16 | | PA | | 2-2 | 34-21-11 | GDX0003 | | S.. | 2 | | | D00367C | 11 | | ALL |
| 010 | 24 | | PK | | 0-7 | 34-21-11 | D00367B | | A01 | | | | SM00001 | | W | 275-299 |
| 012 | 24 | | PK | | 3-6 | 34-21-11 | D04699P | | 12 | | | | D00367B | F01 | | ALL |
| 013 | 24 | | PK | | 3-6 | 34-21-11 | D04699P | | 13 | | | | D00367B | F02 | | ALL |
| 014 | 22 | | PA | | 3-6 | 34-21-11 | D04699P | | 14 | | | | D00367B | E13 | | ALL |
| 015 | 22 | | PA | | 3-8 | 34-21-11 | D04699P | | 15 | | | | TB0161G | 7 | 2 | ALL |
| 016 | 22 | | PA | | 3-8 | 34-21-11 | D04699P | | 16 | | | | TB0161G | 8 | 2 | ALL |
| 017 | 22 | | PA | | 3-9 | 34-21-11 | D04699P | | 17 | | | | TB0161G | 9 | 2 | ALL |
| 018 | 22 | | PA | | 2-11 | 34-21-11 | TB0161G | | 7 | 2 | | | D00367B | E12 | | ALL |
| 019 | 22 | | PA | | 2-11 | 34-21-11 | TB0161G | | 8 | 2 | | | D00367B | E11 | | ALL |
| 020 | 22 | | PA | | 3-0 | 34-21-11 | TB0161G | | 9 | 2 | | | D00367B | E10 | | ALL |
| 021 | 12 | | PA | | 3-2 | 34-21-11 | D00367C | | 7 | | | | D04753P | 1 | | ALL |
| 022 | 22 | | PA | | 3-0 | 34-21-11 | D00367B | E09 | | | | | TB0161G | 10 | 2 | ALL |
| 023 | 22 | | PA | | 3-6 | 34-21-11 | TB0161G | | 7 | 2 | | | D04719P | 2 | | ALL |
| 024 | 22 | | PA | | 3-6 | 34-21-11 | TB0161G | | 8 | 2 | | | D04719P | 1 | | ALL |
| 025 | 22 | | PA | | 3-7 | 34-21-11 | TB0161G | | 9 | 2 | | | D04719P | 3 | | ALL |
| 036 | 24 | | PK | | 4-0 | 34-21-11 | D00367B | J13 | | | | | TB0161G | 44 | 2 | ALL |
| 038 | 22 | | PA | | 2-6 | 22-21-11 | D05371P | | 4 | | | | TB0161G | 10 | 2 | ALL |
| 048 | 22 | | PA | | 3-6 | 33-16-17 | D04699P | | 8 | | | | D00367B | E08 | | ALL |
| 080 | 24 | | PK | | 0-7 | 34-21-11 | D00367B | A01 | | | | | SM00001 | | W | 050-099, 150-199 |
| 081 | 24 | | PK | | 0-7 | 34-21-11 | D00367B | A02 | | | | | SM00001 | | W | ALL |
| 082 | 24 | | PK | | 0-7 | 34-21-11 | D00367B | K09 | | | | | SM00001 | | W | 050-099, 150-199 |
| 083 | 24 | | PK | | 0-7 | 34-21-11 | D00367B | K03 | | | | | SM00001 | | W | 150-199, 275-299 |
| 101 | 24 | | PK | | 4-6 | 34-21-11 | D04719P | | 37 | | | | TB0161G | 44 | 2 | ALL |
| 201B | 24 | | PW | IA | 3-9 | 34-21-11 | D04699P | | 20 | | | | TB0161G | 12 | 2 | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-21-11 | D04699P | | 19 | | | | TB0161G | 11 | 2 | ALL |
| 201Z | | | | IA | 0-0 | 34-21-11 | D04699P | | 21 | | | | GDY0002 | S.. | 2 | ALL |
| 202B | 24 | | PW | IB | 3-7 | 34-21-11 | D04699P | | 23 | | | | TB0161H | 5 | 2 | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-21-11 | D04699P | | 24 | | | | TB0161H | 3 | 2 | ALL |
| 202Z | | | | IB | 0-0 | 34-21-11 | D04699P | | 22 | | | | GDY0001 | S.. | 2 | ALL |
| 203B | 24 | | PW | IC | 3-0 | 34-21-11 | TB0161G | | 12 | 2 | | | D00367B | C06 | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 34-21-11 | TB0161G | | 11 | 2 | | | D00367B | C05 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0160

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0161 | 286T0161 | | | E1-6 L,SHELF (continued) | | | | | | | | | | | |
| 203Z | | | | IC | 0-0 | 34-21-11 | GDY0002 | S.. | 2 | | | D00367B | DED | | ALL |
| 204B | 24 | PW | | ID | 2-10 | 34-21-11 | TB0161H | 5 | 2 | | | D00367B | C11 | | ALL |
| 204R | 24 | PW | | ID | 0-0 | 34-21-11 | TB0161H | 3 | 2 | | | D00367B | C10 | | ALL |
| 204Z | | | | ID | 0-0 | 34-21-11 | GDY0001 | S.. | 2 | | | D00367B | DED | | ALL |
| 205B | 24 | PW | | IE | 3-3 | 34-21-11 | D00367B | K05 | | | | TB0161G | 20 | 2 | ALL |
| 205R | 24 | PW | | IE | 0-0 | 34-21-11 | D00367B | K04 | | | | TB0161G | 19 | 2 | ALL |
| 205Z | | | | IE | 0-0 | 34-21-11 | D00367B | DED | | | | GDY0003 | S.. | 2 | ALL |
| 206B | 24 | PW | | IF | 3-9 | 34-21-11 | TB0161G | 20 | 2 | | | D04719P | 17 | | ALL |
| 206R | 24 | PW | | IF | 0-0 | 34-21-11 | TB0161G | 19 | 2 | | | D04719P | 16 | | ALL |
| 206Z | | | | IF | 0-0 | 34-21-11 | GDY0003 | S.. | 2 | | | D04719P | 18 | | ALL |
| 207 | 20 | UA | | | 1-6 | 34-21-11 | D00367B | | | FD | | GDY0003 | S.. | 2 | ALL |
| 207B | 24 | PW | | IG | 3-3 | 34-21-11 | D00367B | A09 | | | | D04719P | 5 | | ALL |
| 207R | 24 | PW | | IG | 0-0 | 34-21-11 | D00367B | A08 | | | | D04719P | 4 | | ALL |
| 207Z | | | | IG | 0-0 | 34-21-11 | D00367B | | | FD | | D04719P | 6 | | ALL |
| 208B | 24 | PW | | IH | 3-5 | 34-21-11 | D00367B | A14 | | | | TB0161G | 25 | 2 | ALL |
| 208R | 24 | PW | | IH | 0-0 | 34-21-11 | D00367B | A13 | | | | TB0161G | 24 | 2 | ALL |
| 208Z | | | | IH | 0-0 | 34-21-11 | D00367B | DED | | | | GDY0003 | S.. | 2 | ALL |
| 209B | 24 | PW | | II | 4-6 | 34-21-11 | TB0161G | 62 | 2 | | | D00367B | E06 | | ALL |
| 209R | 24 | PW | | II | 0-0 | 34-21-11 | TB0161G | 61 | 2 | | | D00367B | E05 | | ALL |
| 209Z | | | | II | 0-0 | 34-21-11 | GDY0006 | S.. | 2 | | | D00367B | DED | | ALL |
| 210B | 24 | PW | | IJ | 3-1 | 34-21-11 | D00367B | G08 | | | | TB0161G | 14 | 2 | ALL |
| 210R | 24 | PW | | IJ | 0-0 | 34-21-11 | D00367B | G07 | | | | TB0161G | 13 | 2 | ALL |
| 210Z | | | | IJ | 0-0 | 34-21-11 | D00367B | DED | | | | GDY0002 | S.. | 2 | ALL |
| 211B | 24 | PW | | IK | 2-9 | 34-22-91 | D05609P | 6 | | | | TB0161H | 5 | 2 | ALL |
| 211R | 24 | PW | | IK | 0-0 | 34-22-91 | D05609P | 5 | | | | TB0161H | 3 | 2 | ALL |
| 211Z | | | | IK | 0-0 | 34-22-91 | D05609P | 7 | | | | GDY0001 | S.. | 2 | ALL |
| 212B | 24 | PW | | IL | 3-4 | 22-32-11 | TB0161H | 5 | 2 | | | D04719P | 14 | | ALL |
| 212R | 24 | PW | | IL | 0-0 | 22-32-11 | TB0161H | 3 | 2 | | | D04719P | 13 | | ALL |
| 212Z | | | | IL | 0-0 | 22-32-11 | GDY0001 | S.. | 2 | | | D04719P | 15 | | ALL |
| 213B | 24 | PW | | IM | 3-4 | 34-61-12 | TB0161G | 2 | 2 | | | D04719P | 8 | | ALL |
| 213R | 24 | PW | | IM | 0-0 | 34-61-12 | TB0161G | 1 | 2 | | | D04719P | 7 | | ALL |
| 213Z | | | | IM | 0-0 | 34-61-12 | GDY0001 | S.. | 2 | | | D04719P | 9 | | ALL |
| 214B | 24 | PW | | IN | 3-4 | 32-42-11 | TB0161G | 2 | 2 | | | D04719P | 35 | | ALL |
| 214R | 24 | PW | | IN | 0-0 | 32-42-11 | TB0161G | 1 | 2 | | | D04719P | 34 | | ALL |
| 214Z | | | | IN | 0-0 | 32-42-11 | GDY0001 | S.. | 2 | | | D04719P | 36 | | ALL |
| 215B | 24 | PW | | IO | 3-8 | 34-22-38 | D04719P | 52 | | | | TB0161G | 14 | 2 | ALL |
| 215R | 24 | PW | | IO | 0-0 | 34-22-38 | D04719P | 51 | | | | TB0161G | 13 | 2 | ALL |
| 215Z | | | | IO | 0-0 | 34-22-38 | D04719P | 53 | | | | GDY0002 | S.. | 2 | ALL |
| 216B | 24 | PW | | IP | 3-6 | 34-21-11 | D00367B | J11 | | | | TB0161G | 27 | 2 | ALL |

WIRE LIST
D280T132

91-21-11
Section W0160
Page 2
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0161 | 286T0161 | | | E1-6 L,SHELF (continued) | | | | | | | | | | | | |
| 216R | 24 | PW | IP | 0-0 | 34-21-11 | D00367B | | J10 | | | | TB0161G | 26 | 2 | | ALL |
| 216Z | | | IP | 0-0 | 34-21-11 | D00367B | | DED | | | | GDY0004 | S.. | 2 | | ALL |
| 217B | 24 | PW | IQ | 3-10 | 34-61-15 | D04719P | | 32 | | | | TB0161G | 22 | 2 | | ALL |
| 217R | 24 | PW | IQ | 0-0 | 34-61-15 | D04719P | | 31 | | | | TB0161G | 21 | 2 | | ALL |
| 217Z | | | IQ | 0-0 | 34-61-15 | D04719P | | 33 | | | | GDY0003 | S.. | 2 | | ALL |
| 218B | 24 | PW | IR | 3-8 | 34-22-18 | D04719P | | 20 | | | | TB0161G | 14 | 2 | | ALL |
| 218R | 24 | PW | IR | 0-0 | 34-22-18 | D04719P | | 19 | | | | TB0161G | 13 | 2 | | ALL |
| 218Z | | | IR | 0-0 | 34-22-18 | D04719P | | 21 | | | | GDY0002 | S.. | 2 | | ALL |
| 220B | 24 | PW | IT | 2-7 | 22-21-11 | D05371P | | 3 | | | | TB0161G | 14 | 2 | | ALL |
| 220R | 24 | PW | IT | 0-0 | 22-21-11 | D05371P | | 2 | | | | TB0161G | 13 | 2 | | ALL |
| 220Z | | | IT | 0-0 | 22-21-11 | D05371P | | 1 | | | | GDY0002 | S.. | 2 | | ALL |
| 222B | 24 | PW | IV | 2-9 | 34-46-11 | D05609P | | 2 | | | | TB0161G | 2 | 2 | | ALL |
| 222R | 24 | PW | IV | 0-0 | 34-46-11 | D05609P | | 1 | | | | TB0161G | 1 | 2 | | ALL |
| 222Z | | | IV | 0-0 | 34-46-11 | D05609P | | 3 | | | | GDY0001 | S.. | 2 | | ALL |
| 223B | 24 | PW | IW | 2-8 | 34-21-11 | TB0161G | | 2 | 2 | | | TB0161H | 5 | 2 | | ALL |
| 223R | 24 | PW | IW | 0-0 | 34-21-11 | TB0161G | | 1 | 2 | | | TB0161H | 3 | 2 | | ALL |
| 223Z | | | IW | 0-0 | 34-21-11 | GDY0001 | | S.. | 2 | | | TB0161H | DED | | | ALL |
| 225B | 24 | PW | IY | 5-0 | 22-13-11 | D04719P | | 11 | | | | TB0161G | 62 | 2 | | ALL |
| 225R | 24 | PW | IY | 0-0 | 22-13-11 | D04719P | | 10 | | | | TB0161G | 61 | 2 | | ALL |
| 225Z | | | IY | 0-0 | 22-13-11 | D04719P | | 12 | | | | GDY0006 | S.. | 2 | | ALL |
| 226B | 24 | PW | JA | 5-0 | 22-21-21 | D04719P | | 39 | | | | TB0161G | 62 | 2 | | ALL |
| 226R | 24 | PW | JA | 0-0 | 22-21-21 | D04719P | | 38 | | | | TB0161G | 61 | 2 | | ALL |
| 226Z | | | JA | 0-0 | 22-21-21 | D04719P | | 40 | | | | GDY0006 | S.. | 2 | | ALL |
| 227B | 24 | PW | JB | 3-11 | 34-21-21 | D04719P | | 42 | | | | TB0161F | C023 | 2 | | ALL |
| 227R | 24 | PW | JB | 0-0 | 34-21-21 | D04719P | | 41 | | | | TB0161F | A023 | 2 | | ALL |
| 227Z | | | JB | 0-0 | 34-21-21 | D04719P | | 43 | | | | GDY0003 | S.. | 2 | | ALL |
| 228B | 22 | PR | JC | 3-4 | 23-25-13 | D04719P | | 45 | | | | TB0161H | 5 | 2 | | 150, 153-155, 162-165 |
| 228R | 24 | PW | JC | 3-4 | 23-25-13 | D04719P | | 45 | | | | TB0161H | 5 | 2 | | 156-157, 166-199, 277-299 |
| 228Z | | | JC | 0-0 | 23-25-13 | D04719P | | 44 | | | | TB0161H | 3 | 2 | | 150, 153-155, 162-165 |
| 228R | 24 | PW | JC | 0-0 | 23-25-13 | D04719P | | 44 | | | | TB0161H | 3 | 2 | | 156-157, 166-199, 277-299 |
| 228Z | | | JC | 0-0 | 23-25-13 | D04719P | | 46 | | | | GDY0001 | S.. | 2 | | 150, 153-199, 277-299 |
| W0163 | 286T0163 | | | E2-6 SHELF, L HF XCVR | | | | | | | | | | | | |
| 001 | 24 | PK | | 5-0 | 23-11-11 | D00641B | | B05 | | | | D04787P | 1 | | | ALL |
| 002 | 24 | PK | | 5-0 | 23-11-11 | D00641B | | C05 | | | | D04787P | 2 | | | ALL |
| 003 | 24 | PK | | 5-0 | 23-11-11 | D00641C | | 1 | | | | D04787P | 3 | | | ALL |
| 004 | 24 | PK | | 5-0 | 23-11-11 | D00641B | | H05 | | | | D04787P | 4 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0160

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0163 | 286T0163 | | | E2-6 SHELF, L HF XCVR (continued) | | | | | | | | | | | |
| 005 | 24 | | PK | | 5-0 | 23-11-11 | D05709P | | | | D04787P | | 5 | | ALL |
| 006 | 24 | | PK | | 3-0 | 23-11-11 | D05709P | | | | D00641B | | E02 | | ALL |
| 007 | 20 | | PQ | AG | 6-0 | 23-11-11 | D04211P | | | | D00641C | | 2 | | ALL |
| 007Z | | | | AG | 0-0 | 23-11-11 | D04211P | | DED | | D00641C | | DED | | ALL |
| 008 | 20 | | PQ | AH | 6-0 | 23-11-11 | D04211P | | | | D00641C | | 3 | | ALL |
| 008Z | | | | AH | 0-0 | 23-11-11 | D04211P | | DED | | D00641C | | DED | | ALL |
| 009 | 20 | | PQ | AI | 4-0 | 23-11-11 | D00641C | | | | D04787P | | 6 | | ALL |
| 009Z | | | | AI | 0-0 | 23-11-11 | D00641C | | DED | | D04787P | | DED | | ALL |
| 010 | 20 | | PQ | AJ | 5-0 | 23-11-11 | D04211P | | | | TB0163G | | 70 | 2 | ALL |
| 010Z | | | | AJ | 0-0 | 23-11-11 | D04211P | | DED | | TB0163G | | DED | | ALL |
| 011 | 20 | | PQ | AK | 3-0 | 23-11-11 | TB0163G | | | 2 | D00641C | | 7 | | ALL |
| 011Z | | | | AK | 0-0 | 23-11-11 | TB0163G | | DED | | D00641C | | DED | | ALL |
| 012 | 20 | | PA | | 6-0 | 23-11-11 | D04211P | | | | D00641C | | 8 | | ALL |
| 013 | 24 | | PK | | 6-0 | 23-11-11 | D04653P | | | | D00641B | | F05 | | ALL |
| 014 | 24 | | PK | | 6-0 | 23-11-11 | D04653P | | | | D00641B | | E05 | | ALL |
| 015 | 20 | | PA | | 3-0 | 23-11-11 | D00641C | | | | GDX0009 | | S.. | 2 | ALL |
| 016 | 22 | | PQ | AP | 5-0 | 23-11-11 | D04653P | | | | TB0163G | | 70 | 2 | ALL |
| 016Z | | | | AP | 0-0 | 23-11-11 | D04653P | | DED | | TB0163G | | DED | | ALL |
| 017 | 24 | | PK | | 6-0 | 23-11-11 | D04653P | | | | D00641B | | D05 | | ALL |
| 049 | 22 | | PA | | 4-0 | 23-25-14 | D04653P | | | | TB0163G | | 18 | 2 | 150, 153-155, 162-165 |
| 049 | 24 | | PK | | 4-0 | 23-25-14 | D04653P | | | | D06153P | | 15 | | 156-157, 166-199 |
| 049 | 24 | | PK | | 4-0 | 23-25-14 | D04653P | | | | TB0163G | | 18 | 2 | 277-299 |
| 050 | 22 | | PA | | 4-0 | 23-25-14 | D02697 | | X2 | | D04653P | | 12 | | 150, 153-155, 162-165 |
| 050 | 24 | | PK | | 4-0 | 23-25-14 | D02697 | | X2 | | D04653P | | 12 | | 156-157, 166-199, 277-299 |
| 051 | 24 | | PV | CA | 5-0 | 23-25-14 | D02697 | | C1 | | D06153P | | 10 | | 277-299 |
| 051B | 22 | | PR | CA | 6-0 | 23-25-14 | D06153P | | 9 | | D00641B | | | FF | 150, 153-199 |
| 051R | 22 | | PR | CA | 0-0 | 23-25-14 | D06153P | | 10 | | D02697 | | C1 | | 150, 153-199 |
| 051Z | | | | CA | 0-0 | 23-25-14 | D06153P | | | FG | D02697 | | DED | | 150, 153-199 |
| 051Z | | | | CA | 0-0 | 23-25-14 | D02697 | | REF | CA | D06153P | | 9 | | 277-299 |
| 052 | 20 | | PA | | 1-6 | 23-25-14 | TB0163F | | REF | FH | GDX0009 | | S.. | 2 | 150, 153-199 |
| 052 | 24 | | PV | CB | 5-0 | 23-25-14 | D02697 | | B1 | | D06153P | | 11 | | 277-299 |
| 052B | 22 | | PR | CB | 6-0 | 23-25-14 | D06153P | | 12 | | TB0163F | | 11 | 2 | 150, 153-199 |
| 052R | 22 | | PR | CB | 0-0 | 23-25-14 | D06153P | | 11 | | TB0163F | | 10 | 2 | 150, 153-199 |
| 052Z | | | | CB | 0-0 | 23-25-14 | D06153P | | | FG | TB0163F | | REF | | 150, 153-199 |
| 052Z | | | | CB | 0-0 | 23-25-14 | D02697 | | REF | CB | D06153P | | 12 | | 277-299 |
| 053 | 22 | | PA | | 6-0 | 23-25-14 | D06153P | | 13 | | D05709P | | 17 | | 150, 153-155, 162-165 |
| 053 | 24 | | PK | | 6-0 | 23-25-14 | D06153P | | 13 | | D05709P | | 17 | | 156-157, 166-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0160
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0163 | 286T0163 | | | E2-6 SHELF, L HF XCVR (continued) | | | | | | | | | | | | |
| 057 | 22 | | PA | 6-0 | 23-25-14 | D02697 | | A3 | | | D00641B | | C01 | | 150, 153-155, 162-165 | |
| 057 | 24 | | PK | 6-0 | 23-25-14 | D02697 | | A3 | | | D00641B | | C01 | | 156-157, 166-199, 277-299 | |
| 058 | 22 | | PQ | 6-0 | 23-25-14 | D02697 | | B3 | | | D00641B | | A01 | | 150, 153-155, 162-165 | |
| 058 | 24 | | PV | 6-0 | 23-25-14 | D02697 | | B3 | | | D00641B | | A01 | | 156-157, 166-199, 277-299 | |
| 058Z | | | | 0-0 | 23-25-14 | D02697 | | DED | | | D00641B | | | FJ | 150, 153-199 | |
| 058Z | | | | 0-0 | 23-25-14 | D02697 | | REF | CB | | D00641B | | B01 | | 277-299 | |
| 059 | 22 | | PQ | 6-0 | 23-25-14 | D02697 | | C3 | | | D00641B | | D01 | | 150, 153-155, 162-165 | |
| 059 | 24 | | PV | 6-0 | 23-25-14 | D02697 | | C3 | | | D00641B | | D01 | | 156-157, 166-199, 277-299 | |
| 059Z | | | | 0-0 | 23-25-14 | D02697 | | | FE | | D00641B | | | FF | 150, 153-199 | |
| 059Z | | | | 0-0 | 23-25-14 | D02697 | | REF | CA | | D00641B | | E01 | | 277-299 | |
| 060 | 24 | | PV | 5-0 | 23-25-14 | D02697 | | C2 | | | D05709P | | 3 | | 150, 153-199, 277-299 | |
| 060Z | | | | 0-0 | 23-25-14 | D02697 | | | FE | | D05709P | | 4 | | 150, 153-199 | |
| 060Z | | | | 0-0 | 23-25-14 | D02697 | | REF | CA | | D05709P | | 4 | | 277-299 | |
| 061 | 22 | | PA | 4-0 | 23-25-14 | D04211P | | 6 | | | TB0163G | | 14 | 2 | 150, 153-155, 162-165 | |
| 061 | 24 | | PK | 4-0 | 23-25-14 | D04211P | | 6 | | | TB0163G | | 14 | 2 | 156-157, 166-199, 277-299 | |
| 062 | 22 | | PA | 4-0 | 23-25-14 | D04653P | | 1 | | | D06153P | | 8 | | 150, 153-155, 162-165 | |
| 062 | 24 | | PK | 4-2 | 23-25-14 | D04653P | | 1 | | | D06153P | | 8 | | 156-157, 166-199, 277-299 | |
| 063 | 22 | | PA | 4-0 | 23-25-14 | D02697 | | X1 | | | TB0163G | | 14 | 2 | 150, 153-155, 162-165 | |
| 063 | 24 | | PK | 4-0 | 23-25-14 | D02697 | | X1 | | | TB0163G | | 14 | 2 | 156-157, 166-199, 277-299 | |
| 064 | 24 | | PV | 5-0 | 23-25-14 | D02697 | | B2 | | | D05709P | | 5 | | 150, 153-199, 277-299 | |
| 064Z | | | | 0-0 | 23-25-14 | D02697 | | REF | CB | | D05709P | | 6 | | 150, 153-199, 277-299 | |
| 065 | 22 | | PA | 5-0 | 23-25-14 | D02697 | | A2 | | | D05709P | | 7 | | 150, 153-155, 162-165 | |
| 065 | 24 | | PK | 5-0 | 23-25-14 | D02697 | | A2 | | | D05709P | | 7 | | 156-157, 166-199, 277-299 | |
| 066 | 22 | | PA | 5-0 | 23-25-14 | D06153P | | 7 | | | TB0163G | | 18 | 2 | 150, 153-155, 162-165 | |
| 066 | 24 | | PK | 5-0 | 23-25-14 | D06153P | | 7 | | | TB0163G | | 18 | 2 | 156-157, 166-199, 277-299 | |
| 067 | 22 | | PA | 4-0 | 23-25-14 | D02697 | | A1 | | | TB0163G | | 18 | 2 | 150, 153-155, 162-165 | |
| 067 | 24 | | PK | 4-0 | 23-25-14 | D02697 | | A1 | | | TB0163G | | 18 | 2 | 156-157, 166-199, 277-299 | |
| 201 | 20 | | UA | 1-6 | 23-11-11 | GDX0009 | | S.. | 2 | | D00641B | | | FA | ALL | |
| 201B | 24 | | PW | 6-0 | 23-11-11 | D04653P | | 10 | | | D00641B | | H03 | | ALL | |
| 201R | 24 | | PW | 0-0 | 23-11-11 | D04653P | | 9 | | | D00641B | | G03 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0160

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0163 | 286T0163 | | | | E2-6 SHELF, L HF XCVR (continued) | | | | | | | | | | | |
| 201Z | | | | IA | 0-0 | 23-11-11 | D04653P | | 11 | | | | | | FA | ALL |
| 202B | 24 | PL | | IB | 3-0 | 23-21-11 | D05709P | | 2 | | | D00641B | D03 | | | ALL |
| 202R | 24 | PL | | IB | 0-0 | 23-21-11 | D05709P | | 1 | | | D00641B | C03 | | | ALL |
| 203B | 24 | PL | | IC | 3-0 | 23-51-14 | D05709P | | 4 | | | D00641B | E01 | | | 050-099, 151-152, 275-276 |
| 203R | 24 | PL | | IC | 0-0 | 23-51-14 | D05709P | | 3 | | | D00641B | D01 | | | 050-099, 151-152, 275-276 |
| 205B | 22 | PR | | IE | 6-0 | 23-25-13 | D05709P | | 13 | | | D06153P | 3 | | | 150, 153-155, 162-165 |
| 205B | 24 | PW | | IE | 6-0 | 23-25-13 | D05709P | | 13 | | | D06153P | 3 | | | 156-157, 166-199, 277-299 |
| 205R | 22 | PR | | IE | 0-0 | 23-25-13 | D05709P | | 12 | | | D06153P | 2 | | | 150, 153-155, 162-165 |
| 205R | 24 | PW | | IE | 0-0 | 23-25-13 | D05709P | | 12 | | | D06153P | 2 | | | 156-157, 166-199, 277-299 |
| 205Z | | | | IE | 0-0 | 23-25-13 | D05709P | | 8 | | | D06153P | 1 | | | 150, 153-199, 277-299 |
| 206B | 22 | PR | | IF | 6-0 | 23-25-13 | D05709P | | 16 | | | D06153P | 6 | | | 150, 153-155, 162-165 |
| 206B | 24 | PW | | IF | 6-0 | 23-25-13 | D05709P | | 16 | | | D06153P | 6 | | | 156-157, 166-199, 277-299 |
| 206R | 22 | PR | | IF | 0-0 | 23-25-13 | D05709P | | 15 | | | D06153P | 5 | | | 150, 153-155, 162-165 |
| 206R | 24 | PW | | IF | 0-0 | 23-25-13 | D05709P | | 15 | | | D06153P | 5 | | | 156-157, 166-199, 277-299 |
| 206Z | | | | IF | 0-0 | 23-25-13 | D05709P | | 14 | | | D06153P | 4 | | | 150, 153-199, 277-299 |
| 301B | 24 | PM | | MA | 3-0 | 23-51-14 | D05709P | | 6 | | | D00641B | B01 | | | 050-099, 151-152, 275-276 |
| 301R | 24 | PM | | MA | 0-0 | 23-51-14 | D05709P | | 5 | | | D00641B | A01 | | | 050-099, 151-152, 275-276 |
| 301Y | 24 | PM | | MA | 0-0 | 23-51-14 | D05709P | | 7 | | | D00641B | C01 | | | 050-099, 151-152, 275-276 |
| 952 | 20 | PA | | | 1-6 | 23-25-14 | TB0163F | REF | | | FI | GDX0009 | S.. | 2 | | 150, 153-199 |
| 952B | 22 | PR | 1A | | 6-0 | 23-25-14 | TB0163F | | 11 | 2 | | D02697 | D1 | | | 150, 153-199 |
| 952R | 22 | PR | 1A | | 0-0 | 23-25-14 | TB0163F | | 10 | 2 | | D02697 | B1 | | | 150, 153-199 |
| 952Z | | | | 1A | 0-0 | 23-25-14 | TB0163F | REF | | | FI | D02697 | REF | | | 150, 153-199 |
| 958 | 22 | PA | | | 6-0 | 23-25-14 | D00641B | | | | FJ | D02697 | D3 | | | 150, 153-199 |
| 964 | 24 | PK | | | 6-0 | 23-25-14 | D02697 | REF | | | CB | D02697 | D2 | | | 150, 153-199 |
| FRA | | | | | 0-0 | 23-25-14 | D00641B | | E01 | | | D00641B | | | FF | 150, 153-199 |
| FRB | | | | | 0-0 | 23-25-14 | D06153P | | 14 | | | D06153P | | | FG | 150, 153-199 |
| FRC | | | | | 0-0 | 23-25-14 | D00641B | | B01 | | | D00641B | | | FJ | 150, 153-199 |
| W0165 | 286T0165 | | | | E5-1 L,SHELF | | | | | | | | | | | |
| 002 | 20 | PA | | | 2-2 | 34-33-11 | D00401C | | 2 | | | GDX0001 | D.. | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0160
Page 6
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0165 | 286T0165 | | | E5-1 L,SHELF (continued) | | | | | | | | | | | | | |
| 003 | 20 | | PA | | 2-2 | 34-33-11 | D00401C | | | 3 | | | GDX0001 | A.. | 2 | | ALL |
| 004 | 24 | | PK | | 0-3 | 34-33-11 | D00401B | | | J06 | | | D00401B | J04 | | | ALL |
| 005 | 24 | | PK | | 0-3 | 34-33-11 | D00401B | | | C05 | | | D00401B | B05 | | | ALL |
| 006 | 24 | | PK | | 4-5 | 22-12-11 | D00401B | | | K06 | | | D04415P | 6 | | | ALL |
| 007 | 24 | | PK | | 4-5 | 34-33-11 | D04415P | | | 5 | | | D00401B | G05 | | | 050-099 |
| 007 | 24 | | PK | | 4-5 | 34-33-11 | D00401B | | | G05 | | | D04415P | 5 | | | 150-199, 275-299 |
| 008 | 20 | | PQ | AH | 4-5 | 34-33-11 | D00401C | | | 8 | | | D04223P | 1 | | | ALL |
| 008Z | | | | AH | 0-0 | 34-33-11 | D00401C | | | DED | | | D04223P | DED | | | ALL |
| 009 | 24 | | PK | | 0-3 | 34-33-11 | D00401B | | | F02 | | | D00401B | F03 | | | ALL |
| 010 | 24 | | PK | | 4-7 | 34-33-21 | D04415P | | | 4 | | | TB0165F | A001 | 2 | | ALL |
| 015 | 24 | | PK | | 4-7 | 34-33-31 | D04415P | | | 10 | | | TB0165F | C001 | 2 | | ALL |
| 020 | 20 | | PQ | AT | 5-0 | 34-57-11 | D00463C | | | 2 | | | D04575P | 9 | | | ALL |
| 020Z | | | | AT | 0-0 | 34-57-11 | D00463C | | | DED | | | D04575P | DED | | | ALL |
| 021 | 20 | | PA | | 1-10 | 34-57-11 | D00463C | | | 4 | | | GDX0003 | A.. | 2 | | ALL |
| 022 | 20 | | PA | | 1-10 | 34-57-11 | D00463C | | | 3 | | | GDX0003 | D.. | 2 | | ALL |
| 023 | 22 | | PA | | 2-0 | 34-57-11 | D00463B | | | C13 | | | GDX0003 | D.. | 2 | | ALL |
| 024 | 22 | | PA | | 5-3 | 34-57-11 | D00463B | | | C12 | | | D04109P | 12 | | | ALL |
| 025 | 24 | | PK | | 2-11 | 34-33-11 | D00401B | | | F04 | | | TB0165G | 2 | 2 | | ALL |
| 026 | 24 | | PK | | 3-2 | 34-57-11 | D00463B | | | B15 | | | TB0165G | 2 | 2 | | ALL |
| 027 | 24 | | PK | | 4-7 | 34-57-11 | D04415P | | | 11 | | | TB0165G | 2 | 2 | | ALL |
| 028 | 24 | | PK | | 2-4 | 34-33-11 | D00401B | | | F05 | | | GDX0001 | D.. | 2 | | ALL |
| 029 | 24 | | PK | | 2-4 | 34-33-11 | D00401B | | | F06 | | | GDX0001 | D.. | 2 | | ALL |
| 031 | 24 | | PK | | 3-2 | 34-57-11 | D00463B | | | C05 | | | TB0165G | 9 | 2 | | ALL |
| 032 | 24 | | PK | | 3-2 | 34-57-11 | D00463B | | | C07 | | | TB0165G | 9 | 2 | | ALL |
| 033 | 24 | | PK | | 3-2 | 34-57-11 | D00463B | | | C09 | | | TB0165G | 9 | 2 | | ALL |
| 201 | 20 | | UA | | 1-6 | 34-33-11 | D00401B | | | REF | IA | | GDX0001 | S.. | 2 | | ALL |
| 201B | 24 | | PW | IA | 4-5 | 34-33-11 | D00401B | | | G03 | | | D04415P | 3 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-33-11 | D00401B | | | G02 | | | D04415P | 2 | | | ALL |
| 201Z | | | | IA | 0-0 | 34-33-11 | D00401B | | | REF | IA | | D04415P | 1 | | | ALL |
| 202 | 20 | | UA | | 1-6 | 22-12-11 | D00401B | | | REF | IB | | GDX0001 | S.. | 2 | | ALL |
| 202B | 24 | | PW | IB | 4-5 | 22-12-11 | D00401B | | | B03 | | | D04415P | 8 | | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 22-12-11 | D00401B | | | B02 | | | D04415P | 7 | | | ALL |
| 202Z | | | | IB | 0-0 | 22-12-11 | D04415P | | | 9 | | | D00401B | REF | | IB | ALL |
| 208B | 24 | | PL | IH | 5-0 | 23-51-13 | D04579P | | | 2 | | | D00463B | B02 | | | ALL |
| 208R | 24 | | PL | IH | 0-0 | 23-51-13 | D04579P | | | 1 | | | D00463B | B01 | | | ALL |
| 209 | 20 | | UA | | 1-6 | 31-35-13 | TB0165Y | | | REF | II | | GDX0001 | S.. | 2 | | 050-099, 150-199 |
| 209 | 20 | | UA | | 2-1 | 31-35-13 | TB0165Y | | | REF | II | | GDX0001 | S.. | 2 | | 275-299 |
| 209B | 24 | | PW | II | 4-4 | 31-35-13 | TB0165Y | | | C012 | BJ | | D04579P | 7 | | | 050-099 |
| 209B | 24 | | PW | II | 4-4 | 31-35-13 | D04579P | | | 7 | | | TB0165Y | C012 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0160

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|-------------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0165 | 286T0165 | | | E5-1 L,SHELF (continued) | | | | | | | | | | | |
| 209R | 24 | PW | II | | 0-0 | 31-35-13 | TB0165Y | A012 | BJ | | D04579P | 6 | | | 050-099 |
| 209R | 24 | PW | II | | 0-0 | 31-35-13 | D04579P | 6 | | | TB0165Y | A012 | BJ | | 150-199, 275-299 |
| 209Z | | | II | | 0-0 | 31-35-13 | TB0165Y | REF | | II | D04579P | 8 | | | 050-099 |
| 209Z | | | II | | 0-0 | 31-35-13 | D04579P | 8 | | | TB0165Y | REF | | II | 150-199, 275-299 |
| 210 | 20 | UA | | | 1-6 | 34-57-11 | TB0165Y | REF | | IJ | GDX0001 | S.. | 2 | | ALL |
| 210B | 24 | PW | IJ | | 4-5 | 34-57-11 | D04575P | 11 | | | TB0165Y | C012 | BJ | | ALL |
| 210R | 24 | PW | IJ | | 0-0 | 34-57-11 | D04575P | 12 | | | TB0165Y | A012 | BJ | | ALL |
| 210Z | | | IJ | | 0-0 | 34-57-11 | D04575P | 10 | | | TB0165Y | REF | | IJ | ALL |
| 221 | 20 | UA | | | 1-6 | 34-57-11 | TB0165Y | REF | | IU | GDX0001 | S.. | 2 | | ALL |
| 221B | 24 | PW | IU | | 3-2 | 34-57-11 | D00463B | B08 | | | TB0165Y | C012 | BJ | | ALL |
| 221R | 24 | PW | IU | | 0-0 | 34-57-11 | D00463B | B07 | | | TB0165Y | A012 | BJ | | ALL |
| 221Z | | | IU | | 0-0 | 34-57-11 | TB0165Y | REF | | IU | D00463B | DED | | | ALL |
| 222 | 20 | UA | | | 1-6 | 34-57-11 | D00463B | REF | | IV | GDX0003 | S.. | 2 | | ALL |
| 222B | 24 | 7P | IV | | 5-3 | 34-57-11 | D00463B | D02 | | | D04109P | 2 | | | ALL |
| 222BN | 24 | 7P | IV | | 0-0 | 34-57-11 | D00463B | D01 | | | D04109P | 1 | | | ALL |
| 222Z | | | IV | | 0-0 | 34-57-11 | D04109P | 3 | | | D00463B | REF | | IV | ALL |
| 223 | 20 | UA | | | 1-6 | 34-57-11 | D00463B | REF | | IW | GDX0003 | S.. | 2 | | ALL |
| 223B | 24 | 7P | IW | | 5-3 | 34-57-11 | D00463B | D08 | | | D04109P | 5 | | | ALL |
| 223BN | 24 | 7P | IW | | 0-0 | 34-57-11 | D00463B | D07 | | | D04109P | 4 | | | ALL |
| 223Z | | | IW | | 0-0 | 34-57-11 | D04109P | 6 | | | D00463B | REF | | IW | ALL |
| 224 | 20 | UA | | | 1-6 | 34-57-11 | D00463B | REF | | IX | GDX0003 | S.. | 2 | | ALL |
| 224B | 24 | 7P | IX | | 5-3 | 34-57-11 | D00463B | D15 | | | D04109P | 8 | | | ALL |
| 224BN | 24 | 7P | IX | | 0-0 | 34-57-11 | D00463B | D14 | | | D04109P | 7 | | | ALL |
| 224Z | | | IX | | 0-0 | 34-57-11 | D04109P | 9 | | | D00463B | REF | | IX | ALL |
| 225B | 22 | PB | IY | | 5-3 | 34-57-11 | D00463B | C11 | | | D04109P | 11 | | | ALL |
| 225R | 22 | PB | IY | | 0-0 | 34-57-11 | D00463B | C10 | | | D04109P | 10 | | | ALL |
| 227B | 24 | PL | JB | | 4-4 | 23-51-13 | D04579P | 5 | | | TB0165F | C008 | 2 | | ALL |
| 227R | 24 | PL | JB | | 0-0 | 23-51-13 | D04579P | 4 | | | TB0165F | A008 | 2 | | ALL |
| 228 | 20 | UA | | | 1-6 | 34-22-18 | D00463B | | | JC | GDX0003 | S.. | 2 | | 050-099 |
| 228 | 20 | UA | | | 2-0 | 34-22-18 | D00463B | REF | | JC | GDX0003 | S.. | 2 | | 150-199, 275-299 |
| 228B | 24 | PW | JC | | 5-3 | 34-22-18 | D00463B | B14 | | | D04415P | 17 | | | 050-099 |
| 228B | 24 | PW | JC | | 5-3 | 34-22-18 | D04415P | 17 | | | D00463B | B14 | | | 150-199, 275-299 |
| 228R | 24 | PW | JC | | 0-0 | 34-22-18 | D00463B | B13 | | | D04415P | 16 | | | 050-099 |
| 228R | 24 | PW | JC | | 0-0 | 34-22-18 | D04415P | 16 | | | D00463B | B13 | | | 150-199, 275-299 |
| 228Z | | | JC | | 0-0 | 34-22-18 | D00463B | | | JC | D04415P | 18 | | | 050-099 |
| 228Z | | | JC | | 0-0 | 34-22-18 | D04415P | 18 | | | D00463B | REF | | JC | 150-199, 275-299 |
| 229 | 20 | UA | | | 1-6 | 34-22-28 | TB0165G | REF | | JD | GDX0002 | S.. | 2 | | 050-099 |
| 229 | 20 | UA | | | 2-3 | 34-22-28 | GDX0002 | S.. | 2 | | TB0165G | REF | | JD | 150-199, 275-299 |
| 229B | 24 | PW | JD | | 4-7 | 34-22-28 | D04415P | 20 | | | TB0165G | 20 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0160

Page 8

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0165 | 286T0165 | | | E5-1 L,SHELF (continued) | | | | | | | | | | | |
| 229R | 24 | PW | JD | | 0-0 | 34-22-28 | D04415P | 19 | | | TB0165G | 19 | 2 | | ALL |
| 229Z | | | JD | | 0-0 | 34-22-28 | D04415P | 21 | | | TB0165G | REF | | JD | ALL |
| 230 | 20 | UA | | | 1-6 | 34-22-81 | TB0165G | REF | JE | | GDX0002 | S.. | 2 | | 050-099 |
| 230 | 20 | UA | | | 2-3 | 34-22-81 | TB0165G | REF | JE | | GDX0002 | S.. | 2 | | 150-199, 275-299 |
| 230B | 24 | PW | JE | | 3-2 | 34-22-81 | D00463B | B11 | | | TB0165G | 20 | 2 | | ALL |
| 230R | 24 | PW | JE | | 0-0 | 34-22-81 | D00463B | B10 | | | TB0165G | 19 | 2 | | ALL |
| 230Z | | | JE | | 0-0 | 34-22-81 | D00463B | DED | | | TB0165G | REF | | JE | ALL |
| 231 | 20 | UA | | | 1-6 | 34-22-81 | TB0165G | REF | JF | | GDX0002 | S.. | 2 | | 050-099 |
| 231 | 20 | UA | | | 2-3 | 34-22-81 | TB0165G | REF | JF | | GDX0002 | S.. | 2 | | 150-199, 275-299 |
| 231B | 24 | PW | JF | | 3-5 | 34-22-81 | D04153P | 2 | | | TB0165G | 20 | 2 | | ALL |
| 231R | 24 | PW | JF | | 0-0 | 34-22-81 | D04153P | 1 | | | TB0165G | 19 | 2 | | ALL |
| 231Z | | | JF | | 0-0 | 34-22-81 | D04153P | 3 | | | TB0165G | REF | | JF | ALL |

WIRE LIST
D280T132

91-21-11
Section W0160
Page 9 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0171 | 286T0171 | | | E1-6 R,SHELF | | | | | | | | | | | |
| 002 | 22 | | PA | | 4-9 | 22-21-21 | TB0161G | 55 | 2 | | D05373P | 15 | | | ALL |
| 003 | 22 | | PA | | 6-0 | 34-21-21 | D04761P | 3 | | | D00371B | D01 | | | ALL |
| 004 | 22 | | PA | | 6-0 | 34-21-21 | D04761P | 4 | | | D00371B | D02 | | | ALL |
| 005 | 22 | | PA | | 6-0 | 34-21-21 | D04761P | 5 | | | D00371B | D03 | | | ALL |
| 006 | 24 | | PV | AF | 3-0 | 34-21-21 | D04245P | 1 | | | D00371C | 1 | | | ALL |
| 006Z | | | | AF | 0-0 | 34-21-21 | D04245P | | DED | | D00371C | DED | | | ALL |
| 007 | 20 | | PA | | 2-0 | 34-21-21 | GDX0009 | A.. | 2 | | D00371C | 5 | | | ALL |
| 008 | 16 | | PA | | 2-0 | 34-21-21 | GDX0009 | D.. | 2 | | D00371C | 8 | | | ALL |
| 009 | 16 | | PA | | 2-0 | 34-21-21 | GDX0009 | S.. | 2 | | D00371C | 11 | | | ALL |
| 010 | 24 | | PK | | 1-3 | 34-21-21 | SM00001 | | W | | D00371B | A02 | | | 275-299 |
| 012 | 24 | | PK | | 6-0 | 34-21-21 | D04761P | 12 | | | D00371B | F01 | | | ALL |
| 013 | 24 | | PK | | 6-0 | 34-21-21 | D04761P | 13 | | | D00371B | F02 | | | ALL |
| 014 | 22 | | PA | | 6-0 | 34-21-21 | D04761P | 14 | | | D00371B | E13 | | | ALL |
| 015 | 22 | | PA | | 5-4 | 34-21-21 | D04761P | 15 | | | TB0161G | 52 | 2 | | ALL |
| 016 | 22 | | PA | | 5-4 | 34-21-21 | D04761P | 16 | | | TB0161G | 53 | 2 | | ALL |
| 017 | 22 | | PA | | 5-4 | 34-21-21 | D04761P | 17 | | | TB0161G | 54 | 2 | | ALL |
| 018 | 22 | | PA | | 4-8 | 34-21-21 | TB0161G | 52 | 2 | | D00371B | E12 | | | ALL |
| 019 | 22 | | PA | | 4-8 | 34-21-21 | TB0161G | 53 | 2 | | D00371B | E11 | | | ALL |
| 020 | 22 | | PA | | 4-8 | 34-21-21 | TB0161G | 54 | 2 | | D00371B | E10 | | | ALL |
| 021 | 12 | | PA | | 5-0 | 34-21-21 | D00371C | 7 | | | D05619P | 14 | | | ALL |
| 022 | 22 | | PA | | 4-8 | 34-21-21 | D00371B | E09 | | | TB0161G | 55 | 2 | | ALL |
| 023 | 22 | | PA | | 3-5 | 31-31-14 | D05373P | 4 | | | D04769P | 53 | | | ALL |
| 036 | 24 | | PK | | 4-2 | 34-21-21 | D00371B | J13 | | | D04769P | 37 | | | ALL |
| 048 | 22 | | PA | | 6-0 | 33-16-17 | D04761P | 8 | | | D00371B | E08 | | | ALL |
| 050 | 22 | | PA | | 3-5 | 22-21-21 | D05373P | 1 | | | D04769P | 20 | | | ALL |
| 053 | 22 | | PA | | 4-10 | 34-21-21 | TB0161G | 52 | 2 | | D04769P | 40 | | | ALL |
| 054 | 22 | | PA | | 4-10 | 34-21-21 | TB0161G | 53 | 2 | | D04769P | 38 | | | ALL |
| 055 | 22 | | PA | | 4-10 | 34-21-21 | TB0161G | 54 | 2 | | D04769P | 39 | | | ALL |
| 080 | 24 | | PK | | 1-3 | 34-21-21 | D00371B | A01 | | | SM00001 | | W | | ALL |
| 081 | 24 | | PK | | 1-3 | 34-21-21 | D00371B | A02 | | | SM00001 | | W | | 050-099, 150-199 |
| 082 | 24 | | PK | | 1-3 | 34-21-21 | D00371B | K09 | | | SM00001 | | W | | 050-099, 150-199 |
| 083 | 24 | | PK | | 1-3 | 34-21-21 | D00371B | K03 | | | SM00001 | | W | | 150-199, 275-299 |
| 201B | 24 | | PW | IA | 5-4 | 34-21-21 | D04761P | 20 | | | TB0161G | 57 | 2 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-21-21 | D04761P | 19 | | | TB0161G | 56 | 2 | | ALL |
| 201Z | | | | IA | 0-0 | 34-21-21 | D04761P | 21 | | | GDY0006 | S.. | 2 | | ALL |
| 202B | 24 | | PW | IB | 5-4 | 34-21-21 | D04761P | 23 | | | TB0161H | 50 | 2 | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-21-21 | D04761P | 24 | | | TB0161H | 48 | 2 | | ALL |
| 202Z | | | | IB | 0-0 | 34-21-21 | D04761P | 22 | | | GDY0006 | S.. | 2 | | ALL |
| 203B | 24 | | PW | IC | 4-8 | 34-21-21 | TB0161G | 57 | 2 | | D00371B | C06 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0170
Page 1
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0171 | 286T0171 | | | E1-6 R,SHELF (continued) | | | | | | | | | | | | |
| 203R | 24 | PW | IC | 0-0 | 34-21-21 | TB0161G | 56 | 2 | | D00371B | C05 | | | ALL | | |
| 203Z | | | IC | 0-0 | 34-21-21 | GDY0006 | S.. | 2 | | D00371B | DED | | | ALL | | |
| 204B | 24 | PW | ID | 4-8 | 34-21-21 | TB0161H | 50 | 2 | | D00371B | C11 | | | ALL | | |
| 204R | 24 | PW | ID | 0-0 | 34-21-21 | TB0161H | 48 | 2 | | D00371B | C10 | | | ALL | | |
| 204Z | | | ID | 0-0 | 34-21-21 | GDY0006 | S.. | 2 | | D00371B | DED | | | ALL | | |
| 205B | 24 | PW | IE | 4-8 | 34-21-21 | TB0161G | 59 | 2 | | D00371B | K05 | | | ALL | | |
| 205R | 24 | PW | IE | 0-0 | 34-21-21 | TB0161G | 60 | 2 | | D00371B | K04 | | | ALL | | |
| 205Z | | | IE | 0-0 | 34-21-21 | GDY0006 | S.. | 2 | | D00371B | DED | | | ALL | | |
| 206B | 24 | PW | IF | 5-0 | 34-43-21 | TB0161H | 50 | 2 | | D05619P | 9 | | | ALL | | |
| 206R | 24 | PW | IF | 0-0 | 34-43-21 | TB0161H | 48 | 2 | | D05619P | 8 | | | ALL | | |
| 206Z | | | IF | 0-0 | 34-43-21 | GDY0006 | S.. | 2 | | D05619P | 10 | | | ALL | | |
| 207B | 24 | PW | IG | 4-8 | 34-21-21 | TB0161G | 22 | 2 | | D00371B | A09 | | | ALL | | |
| 207R | 24 | PW | IG | 0-0 | 34-21-21 | TB0161G | 21 | 2 | | D00371B | A08 | | | ALL | | |
| 207Z | | | IG | 0-0 | 34-21-21 | GDY0003 | S.. | 2 | | D00371B | DED | | | ALL | | |
| 208B | 24 | PW | IH | 4-10 | 34-21-21 | D04769P | 8 | | | TB0161F | A058 | 2 | | ALL | | |
| 208R | 24 | PW | IH | 0-0 | 34-21-21 | D04769P | 7 | | | TB0161F | C058 | 2 | | ALL | | |
| 208Z | | | IH | 0-0 | 34-21-21 | D04769P | 9 | | | GDY0006 | S.. | 2 | | ALL | | |
| 209B | 24 | PW | II | 4-8 | 22-13-21 | D05619P | 5 | | | TB0161G | 18 | 2 | | ALL | | |
| 209R | 24 | PW | II | 0-0 | 22-13-21 | D05619P | 4 | | | TB0161G | 17 | 2 | | ALL | | |
| 209Z | | | II | 0-0 | 22-13-21 | D05619P | 6 | | | GDY0003 | S.. | 2 | | ALL | | |
| 210B | 24 | PW | IJ | 4-8 | 34-22-81 | D05619P | 17 | | | TB0161H | 50 | 2 | | ALL | | |
| 210R | 24 | PW | IJ | 0-0 | 34-22-81 | D05619P | 19 | | | TB0161H | 48 | 2 | | ALL | | |
| 210Z | | | IJ | 0-0 | 34-22-81 | D05619P | 21 | | | GDY0006 | S.. | 2 | | ALL | | |
| 212B | 24 | PW | IL | 4-10 | 22-32-11 | TB0161H | 50 | 2 | | D04769P | 23 | | | ALL | | |
| 212R | 24 | PW | IL | 0-0 | 22-32-11 | TB0161H | 48 | 2 | | D04769P | 22 | | | ALL | | |
| 212Z | | | IL | 0-0 | 22-32-11 | GDY0006 | S.. | 2 | | D04769P | 24 | | | ALL | | |
| 213B | 24 | PW | IM | 4-10 | 34-61-22 | TB0161G | 47 | 2 | | D04769P | 11 | | | ALL | | |
| 213R | 24 | PW | IM | 0-0 | 34-61-22 | TB0161G | 46 | 2 | | D04769P | 10 | | | ALL | | |
| 213Z | | | IM | 0-0 | 34-61-22 | GDY0005 | S.. | 2 | | D04769P | 12 | | | ALL | | |
| 214B | 24 | PW | IN | 4-10 | 32-42-11 | TB0161G | 47 | 2 | | D04769P | 34 | | | ALL | | |
| 214R | 24 | PW | IN | 0-0 | 32-42-11 | TB0161G | 46 | 2 | | D04769P | 33 | | | ALL | | |
| 214Z | | | IN | 0-0 | 32-42-11 | GDY0005 | S.. | 2 | | D04769P | 35 | | | ALL | | |
| 216B | 24 | PW | IP | 4-8 | 34-21-21 | D00371B | J11 | | | TB0161F | C023 | 2 | | ALL | | |
| 216R | 24 | PW | IP | 0-0 | 34-21-21 | D00371B | J10 | | | TB0161F | A023 | 2 | | ALL | | |
| 216Z | | | IP | 0-0 | 34-21-21 | GDY0003 | S.. | 2 | | D00371B | DED | | | ALL | | |
| 217B | 24 | PW | IQ | 4-10 | 34-61-25 | TB0161G | 25 | 2 | | D04769P | 2 | | | ALL | | |
| 217R | 24 | PW | IQ | 0-0 | 34-61-25 | TB0161G | 24 | 2 | | D04769P | 1 | | | ALL | | |
| 217Z | | | IQ | 0-0 | 34-61-25 | GDY0003 | S.. | 2 | | D04769P | 3 | | | ALL | | |
| 218B | 24 | PW | IR | 4-8 | 34-22-28 | D05619P | 2 | | | TB0161G | 45 | 2 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0171 | 286T0171 | | | E1-6 R,SHELF (continued) | | | | | | | | | | | |
| 218R | 24 | PW | IR | | 0-0 | 34-22-28 | D05619P | | 1 | | TB0161G | 41 | 2 | | ALL |
| 218Z | | | IR | | 0-0 | 34-22-28 | D05619P | | 3 | | GDY0005 | S.. | 2 | | ALL |
| 219B | 24 | PW | IS | | 4-10 | 34-21-21 | D04769P | | 5 | | TB0161G | 59 | 2 | | ALL |
| 219R | 24 | PW | IS | | 0-0 | 34-21-21 | D04769P | | 4 | | TB0161G | 60 | 2 | | ALL |
| 219Z | | | IS | | 0-0 | 34-21-21 | D04769P | | 6 | | GDY0006 | S.. | 2 | | ALL |
| 221B | 24 | PW | IU | | 4-9 | 22-21-21 | D05373P | | 11 | | TB0161G | 45 | 2 | | ALL |
| 221R | 24 | PW | IU | | 0-0 | 22-21-21 | D05373P | | 10 | | TB0161G | 41 | 2 | | ALL |
| 221Z | | | IU | | 0-0 | 22-21-21 | D05373P | | 9 | | GDY0005 | S.. | 2 | | ALL |
| 222B | 24 | PW | IV | | 2-8 | 34-21-21 | TB0161G | | 47 | 2 | TB0161H | 50 | 2 | | ALL |
| 222R | 24 | PW | IV | | 0-0 | 34-21-21 | TB0161G | | 46 | 2 | TB0161H | 48 | 2 | | ALL |
| 222Z | | | IV | | 0-0 | 34-21-21 | GDY0005 | | S.. | 2 | TB0161H | DED | | | ALL |
| 224B | 24 | PW | IX | | 4-8 | 34-21-21 | D00371B | | A14 | | TB0161F | A058 | 2 | | ALL |
| 224R | 24 | PW | IX | | 0-0 | 34-21-21 | D00371B | | A13 | | TB0161F | C058 | 2 | | ALL |
| 224Z | | | IX | | 0-0 | 34-21-21 | D00371B | | DED | | GDY0006 | S.. | 2 | | ALL |
| 225B | 24 | PW | IY | | 4-8 | 34-21-21 | D00371B | | E06 | | TB0161G | 18 | 2 | | ALL |
| 225R | 24 | PW | IY | | 0-0 | 34-21-21 | D00371B | | E05 | | TB0161G | 17 | 2 | | ALL |
| 225Z | | | IY | | 0-0 | 34-21-21 | D00371B | | DED | | GDY0003 | S.. | 2 | | ALL |
| 226B | 24 | PW | JA | | 4-8 | 34-21-21 | D00371B | | G08 | | TB0161G | 45 | 2 | | ALL |
| 226R | 24 | PW | JA | | 0-0 | 34-21-21 | D00371B | | G07 | | TB0161G | 41 | 2 | | ALL |
| 226Z | | | JA | | 0-0 | 34-21-21 | D00371B | | DED | | GDY0005 | S.. | 2 | | ALL |
| 227B | 24 | PW | JB | | 4-9 | 22-21-11 | D05397P | | 5 | | TB0161G | 18 | 2 | | ALL |
| 227R | 24 | PW | JB | | 0-0 | 22-21-11 | D05397P | | 4 | | TB0161G | 17 | 2 | | ALL |
| 227Z | | | JB | | 0-0 | 22-21-11 | D05397P | | 6 | | GDY0003 | S.. | 2 | | ALL |
| 228B | 24 | PW | JC | | 4-10 | 34-21-31 | D04769P | | 16 | | TB0161G | 27 | 2 | | ALL |
| 228R | 24 | PW | JC | | 0-0 | 34-21-31 | D04769P | | 15 | | TB0161G | 26 | 2 | | ALL |
| 228Z | | | JC | | 0-0 | 34-21-31 | D04769P | | 32 | | GDY0004 | S.. | 2 | | ALL |
| 229B | 22 | PR | JD | | 4-10 | 23-25-13 | D04769P | | 44 | | TB0161H | 50 | 2 | | 150, 153-155, 162-165 |
| 229B | 24 | PW | JD | | 4-10 | 23-25-13 | D04769P | | 44 | | TB0161H | 50 | 2 | | 156-157, 166-199, 277-299 |
| 229R | 22 | PR | JD | | 0-0 | 23-25-13 | D04769P | | 43 | | TB0161H | 48 | 2 | | 150, 153-155, 162-165 |
| 229R | 24 | PW | JD | | 0-0 | 23-25-13 | D04769P | | 43 | | TB0161H | 48 | 2 | | 156-157, 166-199, 277-299 |
| 229Z | | | JD | | 0-0 | 23-25-13 | D04769P | | 42 | | GDY0006 | S.. | 2 | | 150, 153-199, 277-299 |
| 233B | 24 | PW | JH | | 4-8 | 34-22-29 | D05619P | | 12 | | TB0161G | 59 | 2 | | ALL |
| 233R | 24 | PW | JH | | 0-0 | 34-22-29 | D05619P | | 11 | | TB0161G | 60 | 2 | | ALL |
| 233Z | | | JH | | 0-0 | 34-22-29 | D05619P | | 13 | | GDY0006 | S.. | 2 | | ALL |
| W0173 | 286T0173 | | | E2-6 SHELF,R HF XCVR | | | | | | | | | | | |
| 001 | 24 | PK | | | 4-0 | 23-11-21 | D00643B | | B05 | | D04789P | 1 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0170
Page 3
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0173 | 286T0173 | | | E2-6 SHELF,R HF XCVR (continued) | | | | | | | | | | | | |
| 002 | 24 | | PK | 4-0 | 23-11-21 | D00643B | C05 | | | | D04789P | 2 | | | ALL | |
| 003 | 24 | | PK | 4-0 | 23-11-21 | D00643C | 1 | | | | D04789P | 3 | | | ALL | |
| 004 | 24 | | PK | 4-0 | 23-11-21 | D00643B | H05 | | | | D04789P | 4 | | | ALL | |
| 005 | 24 | | PK | 4-0 | 23-11-21 | D05719P | 10 | | | | D04789P | 5 | | | ALL | |
| 006 | 24 | | PK | 3-0 | 23-11-21 | D05719P | 11 | | | | D00643B | E02 | | | ALL | |
| 007 | 20 | | PQ | AG | 5-0 | 23-11-21 | D04255P | 1 | | | D00643C | 2 | | | ALL | |
| 007Z | | | | AG | 0-0 | 23-11-21 | D04255P | DED | | | D00643C | DED | | | ALL | |
| 008 | 20 | | PQ | AH | 5-0 | 23-11-21 | D04255P | 2 | | | D00643C | 3 | | | ALL | |
| 008Z | | | | AH | 0-0 | 23-11-21 | D04255P | DED | | | D00643C | DED | | | ALL | |
| 009 | 20 | | PQ | AI | 4-0 | 23-11-21 | D00643C | 9 | | | D04789P | 6 | | | ALL | |
| 009Z | | | | AI | 0-0 | 23-11-21 | D00643C | DED | | | D04789P | DED | | | ALL | |
| 010 | 20 | | PQ | AJ | 4-0 | 23-11-21 | D04255P | 3 | | | TB0163G | 74 | 2 | | ALL | |
| 010Z | | | | AJ | 0-0 | 23-11-21 | D04255P | DED | | | TB0163G | DED | | | ALL | |
| 011 | 20 | | PQ | AK | 4-0 | 23-11-21 | TB0163G | 74 | 2 | | D00643C | 7 | | | ALL | |
| 011Z | | | | AK | 0-0 | 23-11-21 | TB0163G | DED | | | D00643C | DED | | | ALL | |
| 012 | 20 | | PA | | 5-0 | 23-11-21 | D04255P | 8 | | | D00643C | 8 | | | ALL | |
| 013 | 24 | | PK | | 5-0 | 23-11-21 | D04657P | 4 | | | D00643B | F05 | | | ALL | |
| 014 | 24 | | PK | | 5-0 | 23-11-21 | D04657P | 6 | | | D00643B | E05 | | | ALL | |
| 015 | 20 | | PA | | 3-0 | 23-11-21 | D00643C | 10 | | | GDX0009 | S.. | 2 | | ALL | |
| 016 | 22 | | PQ | AP | 4-0 | 23-11-21 | D04657P | 3 | | | TB0163G | 74 | 2 | | ALL | |
| 016Z | | | | AP | 0-0 | 23-11-21 | D04657P | DED | | | TB0163G | DED | | | ALL | |
| 017 | 24 | | PK | | 5-0 | 23-11-21 | D04657P | 5 | | | D00643B | D05 | | | ALL | |
| 048 | 22 | | PQ | BW | 4-0 | 23-25-14 | D02699 | A3 | | | D00643B | D01 | | | 150, 153-155, 162-165 | |
| 048 | 24 | | PV | BW | 4-0 | 23-25-14 | D02699 | A3 | | | D00643B | D01 | | | 156-157, 166-199, 277-299 | |
| 048Z | | | | BW | 0-0 | 23-25-14 | D02699 | | | CE | D00643B | | | FB | 150, 153-199 | |
| 048Z | | | | BW | 0-0 | 23-25-14 | D02699 | REF | | CE | D00643B | E01 | | | 277-299 | |
| 049 | 22 | | PQ | BX | 4-0 | 23-25-14 | D02699 | B3 | | | D00643B | A01 | | | 150, 153-155, 162-165 | |
| 049 | 24 | | PV | BX | 4-0 | 23-25-14 | D02699 | B3 | | | D00643B | A01 | | | 156-157, 166-199, 277-299 | |
| 049Z | | | | BX | 0-0 | 23-25-14 | D02699 | DED | | | D00643B | | | FA | 150, 153-199 | |
| 049Z | | | | BX | 0-0 | 23-25-14 | D02699 | REF | | CD | D00643B | B01 | | | 277-299 | |
| 050 | 22 | | PA | | 4-0 | 23-25-14 | D02699 | C3 | | | D00643B | C01 | | | 150, 153-155, 162-165 | |
| 050 | 24 | | PK | | 4-0 | 23-25-14 | D02699 | C3 | | | D00643B | C01 | | | 156-157, 166-199, 277-299 | |
| 051 | 22 | | PA | | 5-0 | 23-25-14 | D04657P | 1 | | | D06159P | 2 | | | 150, 153-155, 162-165 | |
| 051 | 24 | | PK | | 5-0 | 23-25-14 | D04657P | 1 | | | D06159P | 2 | | | 156-157, 166-199, 277-299 | |
| 052 | 22 | | PA | | 5-0 | 23-25-14 | D04657P | 2 | | | D06159P | 8 | | | 150, 153-155, 162-165 | |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0173 | 286T0173 | | | E2-6 SHELF,R HF XCVR (continued) | | | | | | | | | | | |
| 052 | 24 | | PK | | 5-0 | 23-25-14 | D04657P | | | | D06159P | | 8 | | 156-157, 166-199 |
| 052 | 24 | | PK | | 6-8 | 23-25-14 | D04657P | | | | TB0163G | 16 | 2 | | 277-299 |
| 053 | 22 | | PA | | 6-0 | 23-25-14 | D04657P | | | | D02699 | | X2 | | 150, 153-155, 162-165 |
| 053 | 24 | | PK | | 6-0 | 23-25-14 | D04657P | | | | D02699 | | X2 | | 156-157, 166-199, 277-299 |
| 054 | 20 | | PA | | 5-0 | 23-25-14 | TB0163F | REF | | FD | GDX0009 | S.. | 2 | | 150, 153-199 |
| 054 | 24 | | PV | CD | 6-0 | 23-25-14 | D06159P | | | | D02699 | | B1 | | 277-299 |
| 054B | 22 | | PR | CD | 5-0 | 23-25-14 | D06159P | | | | TB0163F | 13 | BJ | | 150, 153-199 |
| 054R | 22 | | PR | CD | 0-0 | 23-25-14 | D06159P | | | | TB0163F | 12 | BJ | | 150, 153-199 |
| 054Z | | | | CD | 0-0 | 23-25-14 | D06159P | | | FC | TB0163F | REF | | FD | 150, 153-199 |
| 054Z | | | | CD | 0-0 | 23-25-14 | D06159P | | | | D02699 | REF | | CD | 277-299 |
| 055 | 24 | | PV | CE | 6-0 | 23-25-14 | D06159P | | | | D02699 | | A1 | | 277-299 |
| 055B | 22 | | PR | CE | 5-0 | 23-25-14 | D06159P | | | | D00643B | | | FB | 150, 153-199 |
| 055R | 22 | | PR | CE | 0-0 | 23-25-14 | D06159P | | | | D02699 | | A1 | | 150, 153-199 |
| 055Z | | | | CE | 0-0 | 23-25-14 | D06159P | | | FC | D02699 | DED | | | 150, 153-199 |
| 055Z | | | | CE | 0-0 | 23-25-14 | D06159P | | | | D02699 | REF | | CE | 277-299 |
| 056 | 22 | | PA | | 4-0 | 23-25-14 | D02699 | | | | D05719P | | 7 | | 150, 153-155, 162-165 |
| 056 | 24 | | PK | | 4-0 | 23-25-14 | D02699 | | | | D05719P | | 7 | | 156-157, 166-199, 277-299 |
| 057 | 22 | | PQ | CG | 4-0 | 23-25-14 | D02699 | | | | D05719P | | 5 | | 150, 153-155, 162-165 |
| 057 | 24 | | PV | CG | 4-0 | 23-25-14 | D02699 | | | | D05719P | | 5 | | 156-157, 166-199, 277-299 |
| 057Z | | | | CG | 0-0 | 23-25-14 | D02699 | REF | | FK | D05719P | | 6 | | 150, 153-199 |
| 057Z | | | | CG | 0-0 | 23-25-14 | D02699 | REF | | CD | D05719P | | 6 | | 277-299 |
| 058 | 22 | | PQ | CH | 4-0 | 23-25-14 | D02699 | | | | D05719P | | 3 | | 150, 153-155, 162-165 |
| 058 | 24 | | PV | CH | 4-0 | 23-25-14 | D02699 | | | | D05719P | | 3 | | 156-157, 166-199, 277-299 |
| 058Z | | | | CH | 0-0 | 23-25-14 | D02699 | | | | D05719P | | 4 | | 150, 153-199 |
| 058Z | | | | CH | 0-0 | 23-25-14 | D02699 | REF | | CE | D05719P | | 4 | | 277-299 |
| 059 | 22 | | PA | | 3-0 | 23-25-14 | D02699 | | | | TB0163G | 14 | 2 | | 150, 153-155, 162-165 |
| 059 | 24 | | PK | | 3-0 | 23-25-14 | D02699 | | | | TB0163G | 14 | 2 | | 156-157, 166-199, 277-299 |
| 060 | 22 | | PA | | 6-0 | 23-25-14 | D06159P | | | | TB0163G | 16 | 2 | | 150, 153-155, 162-165 |
| 060 | 24 | | PK | | 6-0 | 23-25-14 | D06159P | | | | TB0163G | 16 | 2 | | 156-157, 166-199, 277-299 |
| 061 | 22 | | PA | | 3-0 | 23-25-14 | D02699 | | | | TB0163G | 16 | 2 | | 150, 153-155, 162-165 |
| 061 | 24 | | PK | | 3-0 | 23-25-14 | D02699 | | | | TB0163G | 16 | 2 | | 156-157, 166-199, 277-299 |
| 201 | 20 | | UA | | 1-6 | 23-11-21 | GDX0009 | S.. | 2 | | D00643B | | | FA | ALL |

WIRE LIST
D280T132

91-21-11
Section W0170
Page 5
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0173 | 286T0173 | | | E2-6 SHELF,R HF XCVR (continued) | | | | | | | | | | | | |
| 201B | 24 | PW | IA | 5-0 | 23-11-21 | D04657P | 10 | | | | D00643B | H03 | | | ALL | |
| 201R | 24 | PW | IA | 0-0 | 23-11-21 | D04657P | 9 | | | | D00643B | G03 | | | ALL | |
| 201Z | | | IA | 0-0 | 23-11-21 | D04657P | 11 | | | | D00643B | | | FA | ALL | |
| 202B | 24 | PL | IB | 3-0 | 23-21-11 | D05719P | 2 | | | | D00643B | D03 | | | ALL | |
| 202R | 24 | PL | IB | 0-0 | 23-21-11 | D05719P | 1 | | | | D00643B | C03 | | | ALL | |
| 203B | 24 | PL | IC | 3-0 | 23-51-14 | D05719P | 4 | | | | D00643B | E01 | | | 050-099, 151-152, 275-276 | |
| 203R | 24 | PL | IC | 0-0 | 23-51-14 | D05719P | 3 | | | | D00643B | D01 | | | 050-099, 151-152, 275-276 | |
| 301B | 24 | PM | MA | 4-0 | 23-51-14 | D05719P | 6 | | | | D00643B | B01 | | | 050-099, 151-152, 275-276 | |
| 301R | 24 | PM | MA | 0-0 | 23-51-14 | D05719P | 5 | | | | D00643B | A01 | | | 050-099, 151-152, 275-276 | |
| 301Y | 24 | PM | MA | 0-0 | 23-51-14 | D05719P | 7 | | | | D00643B | C01 | | | 050-099, 151-152, 275-276 | |
| 949 | 22 | PA | | 5-0 | 23-25-14 | D02699 | | D3 | | | D00643B | | | FA | 150, 153-155, 162-165 | |
| 949 | 24 | PK | | 5-0 | 23-25-14 | D02699 | | D3 | | | D00643B | | | FA | 156-157, 166-199 | |
| 954 | 20 | PA | | 5-0 | 23-25-14 | TB0163F | | REF | | FE | GDX0009 | S.. | 2 | | 150, 153-199 | |
| 954B | 22 | PR | 1A | 5-0 | 23-25-14 | D02699 | | D1 | | | TB0163F | 13 | BJ | | 150, 153-199 | |
| 954R | 22 | PR | 1A | 0-0 | 23-25-14 | D02699 | | B1 | | | TB0163F | 12 | BJ | | 150, 153-199 | |
| 954Z | | | 1A | 0-0 | 23-25-14 | D02699 | | DED | | | TB0163F | | REF | | 150, 153-199 | |
| 957 | 22 | PA | | 5-0 | 23-25-14 | D02699 | | REF | | FK | D02699 | | D2 | | 150, 153-199 | |
| FRA | | | | 0-0 | 23-25-14 | D00643B | | B01 | | | D00643B | | | | 150, 153-199 | |
| FRB | | | | 0-0 | 23-25-14 | D00643B | | E01 | | | D00643B | | | | 150, 153-199 | |
| FRC | | | | 0-0 | 23-25-14 | D06159P | | | | FC | D06159P | | 7 | | 150, 153-199 | |
| W0175 | 286T0175 | | | E5-1 R,SHELF | | | | | | | | | | | | |
| 002 | 20 | PA | | 1-10 | 34-33-21 | D00403C | | 2 | | | GDX0002 | D.. | 2 | | ALL | |
| 003 | 20 | PA | | 1-10 | 34-33-21 | D00403C | | 3 | | | GDX0002 | A.. | 2 | | ALL | |
| 004 | 24 | PK | | 0-3 | 34-33-21 | D00403B | | J06 | | | D00403B | J04 | | | ALL | |
| 005 | 24 | PK | | 0-3 | 34-33-21 | D00403B | | C05 | | | D00403B | B06 | | | ALL | |
| 006 | 24 | PK | | 3-1 | 22-12-21 | D00403B | | K06 | | | D04423P | | 6 | | ALL | |
| 007 | 24 | PK | | 2-9 | 34-33-21 | D00403B | | G05 | | | TB0165F | A001 | 2 | | ALL | |
| 009 | 24 | PK | | 0-3 | 34-33-21 | D00403B | | F02 | | | D00403B | F03 | | | ALL | |
| 010 | 24 | PK | | 2-5 | 34-33-21 | TB0165G | | 7 | 2 | | D04423P | | 4 | | ALL | |
| 011 | 24 | PK | | 2-9 | 34-33-21 | D00403B | | F04 | | | TB0165G | | 7 | 2 | ALL | |
| 020 | 20 | PQ | AT | 4-0 | 34-57-21 | D01419C | | 2 | | | D04577P | | 9 | | 050-099 | |
| 020 | 20 | PQ | AT | 4-0 | 34-57-21 | D04577P | | 9 | | | D01419C | | 2 | | 150-199, 275-299 | |
| 020Z | | | AT | 0-0 | 34-57-21 | D01419C | | DED | | | D04577P | | DED | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0175 | 286T0175 | | | E5-1 R,SHELF (continued) | | | | | | | | | | | |
| 020Z | | | | AT | 0-0 | 34-57-21 | D04577P | | DED | | D01419C | | DED | | 150-199, 275-299 |
| 021 | 20 | | PA | | 1-10 | 34-57-21 | D01419C | | 4 | | GDX0003 | | A.. | 2 | ALL |
| 022 | 20 | | PA | | 1-10 | 34-57-21 | D01419C | | 3 | | GDX0003 | | D.. | 2 | ALL |
| 023 | 22 | | PA | | 2-0 | 34-57-21 | D01419B | | C13 | | GDX0003 | | D.. | 2 | ALL |
| 024 | 22 | | PA | | 5-4 | 34-57-21 | D01419B | | C12 | | D04113P | | | 12 | ALL |
| 026 | 24 | | PK | | 3-3 | 34-57-21 | D01419B | | B15 | | TB0165G | | | 7 2 | ALL |
| 028 | 24 | | PK | | 1-6 | 34-33-21 | D00403B | | F05 | | GDX0002 | | D.. | 2 | ALL |
| 029 | 24 | | PK | | 2-0 | 34-33-21 | D00403B | | F06 | | GDX0002 | | D.. | 2 | 050-099 |
| 029 | 24 | | PK | | 1-6 | 34-33-21 | D00403B | | F06 | | GDX0002 | | D.. | 2 | 150-199, 275-299 |
| 030 | 20 | | PQ | BE | 3-1 | 34-33-21 | D00403C | | 8 | | D04259P | | | 1 | ALL |
| 030Z | | | | BE | 0-0 | 34-33-21 | D00403C | | DED | | D04259P | | DED | | ALL |
| 031 | 24 | | PK | | 3-2 | 34-57-21 | D01419B | | C05 | | TB0165G | | | 10 2 | ALL |
| 032 | 24 | | PK | | 3-2 | 34-57-21 | D01419B | | C07 | | TB0165G | | | 10 2 | ALL |
| 033 | 24 | | PK | | 3-2 | 34-57-21 | D01419B | | C09 | | TB0165G | | | 10 2 | ALL |
| 201 | 20 | | UA | | 1-6 | 34-33-21 | D00403B | | REF | IA | GDX0002 | | S.. | 2 | ALL |
| 201B | 24 | | PW | IA | 3-1 | 34-33-21 | D00403B | | G03 | | D04423P | | | 3 | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-33-21 | D00403B | | G02 | | D04423P | | | 2 | ALL |
| 201Z | | | | IA | 0-0 | 34-33-21 | D00403B | | REF | IA | D04423P | | | 1 | ALL |
| 202 | 20 | | UA | | 1-6 | 22-12-21 | D00403B | | REF | IB | GDX0002 | | S.. | 2 | ALL |
| 202B | 24 | | PW | IB | 3-1 | 22-12-21 | D00403B | | B03 | | D04423P | | | 8 | ALL |
| 202R | 24 | | PW | IB | 0-0 | 22-12-21 | D00403B | | B02 | | D04423P | | | 7 | ALL |
| 202Z | | | | IB | 0-0 | 22-12-21 | D00403B | | REF | IB | D04423P | | | 9 | ALL |
| 208B | 24 | | PL | IH | 3-3 | 23-51-13 | D01419B | | B02 | | TB0165F | | C008 | 2 | ALL |
| 208R | 24 | | PL | IH | 0-0 | 23-51-13 | D01419B | | B01 | | TB0165F | | A008 | 2 | ALL |
| 209 | 20 | | UA | | 1-6 | 31-35-13 | TB0165Y | | REF | II | GDX0002 | | S.. | 2 | 050-099 |
| 209 | 20 | | UA | | 2-0 | 31-35-13 | TB0165Y | | REF | II | GDX0002 | | S.. | 2 | 150-199, 275-299 |
| 209B | 24 | | PW | II | 2-6 | 31-35-13 | TB0165Y | | C011 | BJ | D04423P | | | 12 | 050-099 |
| 209B | 24 | | PW | II | 2-6 | 31-35-13 | D04423P | | 12 | | TB0165Y | | C011 | BJ | 150-199, 275-299 |
| 209R | 24 | | PW | II | 0-0 | 31-35-13 | TB0165Y | | A011 | BJ | D04423P | | | 11 | 050-099 |
| 209R | 24 | | PW | II | 0-0 | 31-35-13 | D04423P | | 11 | | TB0165Y | | A011 | BJ | 150-199, 275-299 |
| 209Z | | | | II | 0-0 | 31-35-13 | TB0165Y | | REF | II | D04423P | | | 13 | 050-099 |
| 209Z | | | | II | 0-0 | 31-35-13 | D04423P | | 13 | | TB0165Y | | REF | | II 150-199, 275-299 |
| 210 | 20 | | UA | | 1-6 | 34-57-21 | TB0165Y | | REF | IJ | GDX0002 | | S.. | 2 | 050-099 |
| 210 | 20 | | UA | | 2-0 | 34-57-21 | TB0165Y | | REF | IJ | GDX0002 | | S.. | 2 | 150-199, 275-299 |
| 210B | 24 | | PW | IJ | 3-1 | 34-57-21 | D04577P | | 11 | | TB0165Y | | C011 | BJ | ALL |
| 210R | 24 | | PW | IJ | 0-0 | 34-57-21 | D04577P | | 12 | | TB0165Y | | A011 | BJ | ALL |
| 210Z | | | | IJ | 0-0 | 34-57-21 | D04577P | | 10 | | TB0165Y | | REF | | IJ ALL |
| 221 | 20 | | UA | | 1-6 | 34-57-21 | TB0165Y | | REF | IU | GDX0002 | | S.. | 2 | 050-099 |
| 221 | 20 | | UA | | 2-0 | 34-57-21 | TB0165Y | | REF | IU | GDX0002 | | S.. | 2 | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11
 Section W0170
 Page 7
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0175 | 286T0175 | | | E5-1 R,SHELF (continued) | | | | | | | | | | | |
| 221B | 24 | PW | IU | | 3-2 | 34-57-21 | D01419B | B08 | | | TB0165Y | C011 | BJ | | ALL |
| 221R | 24 | PW | IU | | 0-0 | 34-57-21 | D01419B | B07 | | | TB0165Y | A011 | BJ | | ALL |
| 221Z | | | IU | | 0-0 | 34-57-21 | D01419B | DED | | | TB0165Y | REF | | IU | ALL |
| 222 | 20 | UA | | | 1-6 | 34-57-21 | D01419B | REF | | IV | GDX0003 | S.. | 2 | | 050-099 |
| 222 | 20 | UA | | | 2-0 | 34-57-21 | D01419B | | | IV | GDX0003 | S.. | 2 | | 150-199, 275-299 |
| 222B | 24 | 7P | IV | | 5-4 | 34-57-21 | D01419B | D02 | | | D04113P | 2 | | | ALL |
| 222BN | 24 | 7P | IV | | 0-0 | 34-57-21 | D01419B | D01 | | | D04113P | 1 | | | ALL |
| 222Z | | | IV | | 0-0 | 34-57-21 | D01419B | REF | | IV | D04113P | 3 | | | 050-099 |
| 222Z | | | IV | | 0-0 | 34-57-21 | D01419B | | | IV | D04113P | 3 | | | 150-199, 275-299 |
| 223 | 20 | UA | | | 1-6 | 34-57-21 | D01419B | REF | | IW | GDX0003 | S.. | 2 | | 050-099 |
| 223 | 20 | UA | | | 2-0 | 34-57-21 | D01419B | | | IW | GDX0003 | S.. | 2 | | 150-199, 275-299 |
| 223B | 24 | 7P | IW | | 5-4 | 34-57-21 | D01419B | D08 | | | D04113P | 5 | | | ALL |
| 223BN | 24 | 7P | IW | | 0-0 | 34-57-21 | D01419B | D07 | | | D04113P | 4 | | | ALL |
| 223Z | | | IW | | 0-0 | 34-57-21 | D01419B | REF | | IW | D04113P | 6 | | | 050-099 |
| 223Z | | | IW | | 0-0 | 34-57-21 | D01419B | | | IW | D04113P | 6 | | | 150-199, 275-299 |
| 224 | 20 | UA | | | 1-6 | 34-57-21 | D01419B | REF | | IX | GDX0003 | S.. | 2 | | 050-099 |
| 224 | 20 | UA | | | 2-0 | 34-57-21 | D01419B | | | IX | GDX0003 | S.. | 2 | | 150-199, 275-299 |
| 224B | 24 | 7P | IX | | 5-4 | 34-57-21 | D01419B | D15 | | | D04113P | 8 | | | ALL |
| 224BN | 24 | 7P | IX | | 0-0 | 34-57-21 | D01419B | D14 | | | D04113P | 7 | | | ALL |
| 224Z | | | IX | | 0-0 | 34-57-21 | D01419B | REF | | IX | D04113P | 9 | | | 050-099 |
| 224Z | | | IX | | 0-0 | 34-57-21 | D01419B | | | IX | D04113P | 9 | | | 150-199, 275-299 |
| 225B | 22 | PB | IY | | 5-4 | 34-57-21 | D01419B | C11 | | | D04113P | 11 | | | 050-099 |
| 225B | 22 | PB | JA | | 5-4 | 34-57-21 | D01419B | C11 | | | D04113P | 11 | | | 150-199, 275-299 |
| 225R | 22 | PB | IY | | 0-0 | 34-57-21 | D01419B | C10 | | | D04113P | 10 | | | 050-099 |
| 225R | 22 | PB | JA | | 0-0 | 34-57-21 | D01419B | C10 | | | D04113P | 10 | | | 150-199, 275-299 |
| 228 | 20 | UA | | | 1-6 | 34-22-28 | D01419B | | | JC | GDX0003 | S.. | 2 | | 050-099 |
| 228 | 20 | UA | | | 2-0 | 34-22-28 | D01419B | | | JC | GDX0003 | S.. | 2 | | 150-199, 275-299 |
| 228B | 24 | PW | JC | | 3-7 | 34-22-28 | D01419B | B14 | | | D04423P | 20 | | | ALL |
| 228R | 24 | PW | JC | | 0-0 | 34-22-28 | D01419B | B13 | | | D04423P | 19 | | | ALL |
| 228Z | | | JC | | 0-0 | 34-22-28 | D01419B | | | JC | D04423P | 21 | | | ALL |
| 229 | 20 | UA | | | 1-6 | 34-22-18 | TB0165G | REF | | JD | GDX0002 | S.. | 2 | | 050-099 |
| 229 | 20 | UA | | | 2-0 | 34-22-18 | GDX0002 | S.. | 2 | | TB0165G | REF | | JD | 150-199, 275-299 |
| 229B | 24 | PW | JD | | 2-9 | 34-22-18 | D04423P | 17 | | | TB0165G | 18 | 2 | | ALL |
| 229R | 24 | PW | JD | | 0-0 | 34-22-18 | D04423P | 16 | | | TB0165G | 17 | 2 | | ALL |
| 229Z | | | JD | | 0-0 | 34-22-18 | D04423P | 18 | | | TB0165G | REF | | JD | ALL |
| 230 | 20 | UA | | | 1-6 | 34-22-91 | TB0165G | REF | | JE | GDX0002 | S.. | 2 | | 050-099 |
| 230 | 20 | UA | | | 2-0 | 34-22-91 | TB0165G | REF | | JE | GDX0002 | S.. | 2 | | 150-199, 275-299 |
| 230B | 24 | PW | JE | | 3-0 | 34-22-91 | D01419B | B11 | | | TB0165G | 18 | 2 | | ALL |
| 230R | 24 | PW | JE | | 0-0 | 34-22-91 | D01419B | B10 | | | TB0165G | 17 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 8

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0175 | 286T0175 | | | E5-1 R,SHELF (continued) | | | | | | | | | | | | | |
| 230Z | | | | JE | 0-0 | 34-22-91 | D01419B | | DED | | | | TB0165G | REF | | JE | ALL |
| 231 | 20 | UA | | | 1-6 | 34-22-91 | TB0165G | | REF | | JF | | GDX0002 | S.. | 2 | | 050-099 |
| 231 | 20 | UA | | | 2-0 | 34-22-91 | TB0165G | | REF | | JF | | GDX0002 | S.. | 2 | | 150-199, 275-299 |
| 231B | 24 | PW | JF | | 3-0 | 34-22-91 | D04967P | | 14 | | | | TB0165G | 18 | 2 | | ALL |
| 231R | 24 | PW | JF | | 0-0 | 34-22-91 | D04967P | | 13 | | | | TB0165G | 17 | 2 | | ALL |
| 231Z | | | | JF | 0-0 | 34-22-91 | D04967P | | 15 | | | | TB0165G | REF | | JF | ALL |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION | | | | | | | | | | | | | |
| 001 | 24 | PK | | | 7-0 | 21-53-11 | D04672J | | 59 | | | | TB0076Z | 12 | BJ | | 050-099 |
| 001 | 24 | PK | | | 7-0 | 21-53-11 | D04672J | | 59 | | | | TB0076Y | A005 | BJ | | 150-199, 275-299 |
| 002 | 24 | PK | | | 7-0 | 21-53-11 | D04672J | | 58 | | | | TB0076Y | C004 | BJ | | ALL |
| 003 | 24 | PK | | | 7-0 | 32-09-11 | D00598 | | 6 | | | | TB0074Z | 10 | BJ | | ALL |
| 004 | 24 | PK | | | 3-0 | 32-09-11 | D00598 | | 12 | | | | TB0076Z | 11 | BJ | | 050-099, 275-299 |
| 004 | 24 | PK | | | 5-0 | 32-09-11 | D00598 | | 12 | | | | TB0076Z | 11 | BJ | | 150-199 |
| 005 | 24 | PK | | | 3-0 | 32-09-11 | D03534 | | 6 | | | | TB0076Z | 8 | BJ | | ALL |
| 006 | 24 | PK | | | 3-0 | 29-32-11 | D05360J | | 17 | | | | D04932J | 27 | | | ALL |
| 009 | 24 | PK | | | 4-0 | 29-31-11 | D04802J | | 6 | | | | D04932J | 24 | | | ALL |
| 010 | 24 | PK | | | 7-0 | 32-09-11 | D03534 | | 12 | | | | TB0074Z | 5 | BJ | | ALL |
| 011 | 24 | PK | | | 6-0 | 32-42-12 | D02912 | | 14 | | | | D04672J | 16 | | | ALL |
| 012 | 24 | PK | | | 6-0 | 32-42-12 | D02912 | | 7 | | | | D04672J | 17 | | | ALL |
| 014 | 24 | PV | AF | | 5-0 | 32-09-11 | D03536 | | X1 | | | | TB0216Z | 13 | BJ | | ALL |
| 014Z | | | AF | | 0-0 | 32-09-11 | D03536 | | DED | | | | TB0216Z | DED | | | ALL |
| 015 | 24 | PV | AI | | 7-0 | 32-09-11 | D03536 | | X2 | | | | TB0074Z | 4 | BJ | | ALL |
| 015Z | | | AI | | 0-0 | 32-09-11 | D03536 | | DED | | | | TB0074Z | DED | | | ALL |
| 016 | 24 | PV | BS | | 6-0 | 32-09-11 | D03514 | | 6 | | | | TB0216Z | 13 | BJ | | ALL |
| 016Z | | | BS | | 0-0 | 32-09-11 | D03514 | | DED | | | | TB0216Z | DED | | | ALL |
| 017 | 24 | PK | | | 5-0 | SPARE | D04802J | | CAP | Y | | | TB0222X | CAP | Y | | 051-099, 150-154 |
| 017 | 24 | PK | | | 5-0 | 21-44-21 | D04802J | | 2 | | | | TB0222X | A017 | BJ | | 275-276 |
| 018 | 24 | PK | | | 5-0 | SPARE | D04802J | | CAP | Y | | | TB0222X | CAP | Y | | 051-099, 150-154 |
| 018 | 24 | PK | | | 5-0 | 21-44-21 | D04802J | | 3 | | | | TB0222X | B017 | BJ | | 275-276 |
| 01A | 24 | PK | | | 4-0 | 21-25-11 | D05360J | | 2 | | | | TB0220Y | C019 | BJ | | ALL |
| 01B | 24 | PK | | | 5-0 | 21-25-11 | SP02256 | | | W | | | TB0220Y | C019 | BJ | | ALL |
| 01C | 24 | PK | | | 5-0 | 21-25-11 | SP02258 | | | W | | | TB0220Y | A012 | BJ | | ALL |
| 01D | 20 | PA | | | 3-0 | 21-25-11 | SP02260 | | | W | | | GDX0008 | D.. | 2 | | ALL |
| 01E | 24 | PK | | | 3-0 | 21-43-11 | D05360J | | 37 | | | | D05658J | 47 | | | 050-099, 150-199 |
| 01E | 24 | PK | | | 5-0 | 21-43-11 | D05360J | | 37 | | | | D05658J | 47 | | | 275-299 |
| 01F | 24 | PK | | | 5-0 | 21-44-11 | D05360J | | 38 | | | | TB0302X | A002 | BJ | | 050-099, 275-299 |
| 01F | 24 | PK | | | 4-0 | 21-44-11 | D05360J | | 38 | | | | TB0302X | A002 | BJ | | 150-199 |
| 01G | 24 | PK | | | 5-0 | 21-44-21 | D04904J | | 16 | | | | TB0302X | A003 | BJ | | 050-099, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 01G | 24 | | PK | 4-0 | 21-44-21 | D04904J | | 16 | | | | | TB0302X | A003 | BJ | | 150-199 |
| 01H | 22 | | PA | 15-0 | 21-28-11 | D13432 | | A2 | | | | | C00664 | 1 | D | | 050-099 |
| 01H | 22 | | PA | 14-0 | 21-28-11 | C00664 | | 1 | D | | | | D13432 | A2 | | | 150-199, 275-299 |
| 01J | 24 | | PK | 6-0 | 21-51-11 | D04672J | | 40 | | | | | TB0216Y | C011 | BJ | | 050-099, 275-299 |
| 01J | 24 | | PK | 4-0 | 21-51-11 | D04672J | | 40 | | | | | TB0216Y | C011 | BJ | | 150-199 |
| 01K | 24 | | PK | 6-0 | 21-51-11 | D04904J | | 58 | | | | | TB0216Y | C011 | BJ | | 050-099, 275-299 |
| 01K | 24 | | PK | 5-0 | 21-51-11 | D04904J | | 58 | | | | | TB0216Y | C011 | BJ | | 150-199 |
| 01L | 24 | | PK | 6-0 | 21-51-11 | D10142 | | 8 | | | | | TB0216Y | C011 | BJ | | ALL |
| 01M | 24 | | PK | 7-0 | 21-51-11 | D04672J | | 21 | | | | | D10142 | 7 | | | ALL |
| 01N | 20 | | PA | 3-0 | 21-53-11 | D10142 | | 9 | | | | | GD0007 | D.. | 2 | | ALL |
| 01P | 24 | | PK | 3-0 | 21-53-11 | D10142 | | 11 | | | | | TB0076X | C001 | BJ | | ALL |
| 01Q | 24 | | PK | 3-0 | 21-53-11 | D10142 | | 12 | | | | | TB0076Y | C004 | BJ | | ALL |
| 01R | 24 | | PK | 3-0 | 21-53-11 | D10142 | | 6 | | | | | TB0076Z | 12 | BJ | | 050-099 |
| 01R | 24 | | PK | 3-0 | 21-53-11 | D10142 | | 6 | | | | | TB0076Y | A005 | BJ | | 150-199, 275-299 |
| 01S | 24 | | PK | 4-0 | 21-58-11 | D04662J | | 9 | | | | | TB0222X | A013 | BJ | | ALL |
| 01U | 18 | | PA | 5-0 | 25-31-31 | D04672J | | 39 | DL | | | | TB0272F | C027 | 2 | | 277-278 |
| 01U | 18 | | PA | 7-0 | 25-31-31 | D04672J | | 39 | DL | | | | TB0272F | C027 | 2 | | 280-299 |
| 01V | 18 | | PA | 5-0 | 25-31-31 | D05894J | | 2 | DK | | | | TB0272F | A027 | 2 | | 277-278 |
| 01V | 18 | | PA | 7-0 | 25-31-31 | D05894J | | 2 | DK | | | | TB0272F | A027 | 2 | | 280-299 |
| 023 | 24 | | PK | 5-0 | 76-11-11 | D05308J | | 1 | | | | | TB0216Y | A006 | BJ | | ALL |
| 024R | 22 | | PH | 4-0 | 26-18-11 | D04672J | | 27 | | | | | D04932J | 31 | | | ALL |
| 025 | 24 | | PK | 4-0 | 36-11-31 | D04932J | | 29 | | | | | D05658J | 22 | | | ALL |
| 026 | 24 | | PK | 4-0 | 36-11-31 | D04932J | | 21 | | | | | D05658J | 23 | | | ALL |
| 027 | 20 | | PA | 3-0 | 36-11-31 | D03480 | | A3 | | | | | GD0005 | D.. | 2 | | 050-099, 275-299 |
| 027 | 20 | | PA | 2-0 | 36-11-31 | D03480 | | A3 | | | | | GD0005 | D.. | 2 | | 150-199 |
| 028 | 24 | | PK | 7-0 | 36-11-31 | D04932J | | 20 | | | | | D03480 | X2 | | | 050-099, 275-299 |
| 028 | 24 | | PK | 6-0 | 36-11-31 | D04932J | | 20 | | | | | D03480 | X2 | | | 150-199 |
| 029 | 22 | | PA | 7-0 | 36-11-31 | D03480 | | A2 | | | | | D05658J | 24 | | | 050-099, 275-299 |
| 029 | 22 | | PA | 6-0 | 36-11-31 | D03480 | | A2 | | | | | D05658J | 24 | | | 150-199 |
| 02C | 20 | | PA | 2-0 | 36-11-61 | D10160 | | A1 | | | | | GD0017 | D.. | 2 | | ALL |
| 02F | 24 | | PK | 20-0 | 28-22-12 | D05658J | | 4 | | | | | D04906J | 5 | | | 050-099, 275-299 |
| 02F | 24 | | PK | 20-0 | 28-22-12 | D05658J | | 4 | | | | | TB0218X | B012 | BJ | | 150-199 |
| 02H | 22 | | PA | 15-0 | 28-22-12 | D04672J | | 18 | | | | | TB0216Z | 19 | BJ | | 050-099, 150-157, 275-278 |
| 02H | 22 | | PA | 15-0 | 28-22-12 | D04672J | | 18 | | | | | TB0216Z | 14 | BJ | | 162-199, 280-299 |
| 02L | 24 | | PK | 4-0 | 77-35-11 | D05360J | | 47 | | | | | D05300J | 46 | | | 050-099, 277-299 |
| 02L | 24 | | PK | 3-0 | 77-35-11 | D05360J | | 47 | | | | | D05300J | 46 | | | 150-199 |
| 02L | 24 | | PK | 4-0 | 77-35-11 | D05360J | | 47 | | | | | D05300J | 55 | | | 275-276 |
| 02N | 24 | | PK | 2-0 | 78-36-11 | D10164 | | 4 | | | | | D10166 | 2 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 10

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 02R | 24 | | PK | | 4-0 | 78-36-11 | D10164 | | | 7 | | | TB0220Y | A019 | BJ | | ALL |
| 02S | 20 | | PA | | 2-0 | 78-36-11 | D10164 | | | 3 | | | GDX0017 | D.. | 2 | | ALL |
| 02T | 24 | | PK | | 3-0 | 78-36-11 | D10166 | | | 4 | | | TB0250Y | A001 | BJ | | ALL |
| 02U | 24 | | PK | | 9-0 | 78-36-11 | D10166 | | | 8 | | | D03492 | A2 | | | 050-099, 150-156, 162-199, 275-299 |
| 02U | 24 | | PK | | 6-0 | 78-36-11 | D10166 | | | 8 | | | D03492 | A2 | | | 157 |
| 02V | 24 | | PK | | 10-0 | 78-36-11 | D10166 | | | 1 | | | D04709J | 16 | | | ALL |
| 02W | 24 | | PK | | 2-0 | 78-36-11 | D10166 | | | 6 | | | D10164 | 1 | | | ALL |
| 02X | 24 | | PK | | 4-0 | 78-36-11 | D10166 | | | 7 | | | TB0220Y | C002 | BJ | | ALL |
| 02Y | 20 | | PA | | 2-0 | 78-36-11 | D10166 | | | 3 | | | GDX0017 | D.. | 2 | | ALL |
| 02Z | 20 | | PA | | 5-0 | 78-36-11 | M10440 | | | B | C | | GDX0017 | D.. | 2 | | 050-099, 150-154 |
| 02Z | 20 | | PA | | 4-0 | 78-36-11 | M10440 | | | B | C | | GDX0017 | D.. | 2 | | 155-199, 275-299 |
| 030 | 24 | | PK | | 2-0 | 36-11-31 | D03480 | | | X1 | | | TB0074Y | C011 | BJ | | ALL |
| 031 | 24 | | PK | | 6-0 | 36-11-31 | D05658J | | | 21 | | | TB0074Y | C011 | BJ | | ALL |
| 033 | 22 | | PA | | 6-0 | 36-11-31 | D05658J | | | 25 | | | D03478 | A2 | | | ALL |
| 034 | 24 | | PK | | 3-0 | 36-11-31 | D03478 | | | X1 | | | TB0074Y | C011 | BJ | | ALL |
| 035 | 20 | | PA | | 3-0 | 36-11-31 | GDX0005 | | | D.. | 2 | | D03478 | A3 | | | 050-099, 275-299 |
| 035 | 20 | | PA | | 2-0 | 36-11-31 | GDX0005 | | | D.. | 2 | | D03478 | A3 | | | 150-199 |
| 036 | 24 | | PK | | 6-0 | 36-11-31 | D04932J | | | 19 | | | D03478 | X2 | | | ALL |
| 037 | 24 | | PV | | 3-0 | 32-09-11 | D03514 | | | 12 | | | TB0076Y | A003 | BJ | | ALL |
| 037Z | | | | BT | 0-0 | 32-09-11 | D03514 | | | DED | | | TB0076Y | DED | | | ALL |
| 038 | 24 | | PK | | 7-0 | 32-09-11 | D03532 | | | 6 | | | TB0076Z | 7 | BJ | | 050-099 |
| 038 | 24 | | PK | | 6-0 | 32-09-11 | D03532 | | | 6 | | | TB0076Z | 7 | BJ | | 150-199, 275-299 |
| 039 | 24 | | PK | | 6-0 | 32-09-11 | D03612 | | | 6 | | | TB0076Z | 8 | BJ | | ALL |
| 03A | 24 | | PK | | 5-0 | 75-23-11 | D10346 | | | A3 | | | D05306J | 2 | | | ALL |
| 03B | 24 | | PK | | 5-0 | 75-23-11 | D10346 | | | A2 | | | D05360J | 25 | | | ALL |
| 03C | 24 | | PK | | 5-0 | 75-23-11 | D10346 | | | A1 | | | D05306J | 4 | | | ALL |
| 03D | 24 | | PK | | 5-0 | 75-23-11 | D10346 | | | X1 | | | D05306J | 5 | | | ALL |
| 03E | 24 | | PK | | 5-0 | 75-23-11 | D10346 | | | X2 | | | D05306J | 6 | | | ALL |
| 03K | 22 | | PA | | 5-0 | 29-32-11 | D04932J | | | 18 | | | TB0302Y | C014 | BJ | | ALL |
| 03L | 24 | | PK | | 5-0 | 29-32-11 | D05360J | | | 52 | | | TB0302Y | C014 | BJ | | ALL |
| 03R | 22 | | PA | | 5-0 | 78-36-11 | M10440 | | | A | C | | D05832J | 41 | | | ALL |
| 03S | 24 | | PK | | 11-0 | 78-36-11 | D04709J | | | 18 | | | TB0250Y | A001 | BJ | | ALL |
| 03T | 20 | | PQ | HG | 8-0 | 78-34-11 | D03536 | | | C2 | | | TB0220Y | A019 | BJ | | 050-099, 150-166, 275-276, 280-299 |
| 03T | 20 | | PQ | HG | 5-0 | 78-34-11 | D03536 | | | C2 | | | TB0220Y | A019 | BJ | | 167-199, 277-278 |
| 03TZ | | | | HG | 0-0 | 78-34-11 | D03536 | | | DED | | | TB0220Y | | | HL | ALL |
| 03U | 22 | | PA | | 5-0 | 27-13-11 | D04906J | | | 14 | | | TB0302Y | C012 | BJ | | ALL |
| 03V | 22 | | PA | | 5-0 | 27-13-11 | D05360J | | | 5 | | | TB0302Y | C012 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 11

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 03W | 22 | | PA | | 5-0 | 27-23-11 | D05360J | | | 14 | | | TB0302Y | A013 | BJ | | ALL |
| 03X | 22 | | PA | | 5-0 | 27-23-11 | D05312J | | | 5 | | | TB0302Y | A013 | BJ | | ALL |
| 03Y | 22 | | PQ | BM | 5-0 | 27-23-11 | D05310J | | | 5 | | | TB0302Y | C013 | BJ | | ALL |
| 03YZ | | | | BM | 0-0 | 27-23-11 | D05310J | | DED | | | | TB0302Y | DED | | | ALL |
| 040 | 24 | | PK | | 4-0 | 32-71-11 | D05780J | | | 4 | | | TB0272F | A029 | 2 | | 150-199 |
| 040 | 24 | | PK | | 5-0 | 32-71-11 | D05780J | | | 4 | | | TB0272F | A029 | 2 | | 275-299 |
| 041 | 18 | | PA | | 4-0 | 32-71-11 | D05310J | | | 8 | DK | | TB0272F | C028 | 2 | | 150-199 |
| 041 | 18 | | PA | | 5-0 | 32-71-11 | D05310J | | | 8 | DK | | TB0272F | C028 | 2 | | 275-299 |
| 042 | 18 | | PA | | 4-0 | 32-71-11 | D05310J | | | 10 | DK | | TB0272F | A028 | 2 | | 150-199 |
| 042 | 18 | | PA | | 5-0 | 32-71-11 | D05310J | | | 10 | DK | | TB0272F | A028 | 2 | | 275-299 |
| 045 | 24 | | PK | | 3-0 | 32-09-11 | D03612 | | | 12 | | | TB0074Y | A007 | BJ | | ALL |
| 046 | 22 | | PA | | 6-0 | 22-14-31 | D05433J | | | 1 | | | TB0076Y | A006 | BJ | | 050-099, 275-299 |
| 046 | 22 | | PA | | 7-0 | 22-14-31 | D05433J | | | 1 | | | TB0076Y | A006 | BJ | | 150-199 |
| 047 | 22 | | PA | | 6-0 | 22-14-31 | D05433J | | | 2 | | | TB0076Y | C006 | BJ | | 050-099, 275-299 |
| 047 | 22 | | PA | | 7-0 | 22-14-31 | D05433J | | | 2 | | | TB0076Y | C006 | BJ | | 150-199 |
| 04B | 24 | | PK | | 7-0 | 32-09-11 | D01736 | | | X1 | | | TB0076Z | | 8 | BJ | ALL |
| 04C | 24 | | PK | | 3-0 | 32-09-11 | D01736 | | | X2 | | | TB0074Y | A007 | BJ | | ALL |
| 04D | 24 | | PK | | 7-0 | 32-09-11 | D04802J | | | 12 | | | TB0074Y | A007 | BJ | | ALL |
| 04E | 24 | | PK | | 6-0 | 32-09-11 | D05360J | | | 33 | | | TB0074Y | C012 | BJ | | ALL |
| 04F | 24 | | PK | | 5-0 | 32-09-11 | D05360J | | | 34 | | | TB0218Y | A006 | BJ | | ALL |
| 04G | 24 | | PK | | 6-0 | 32-09-11 | D04672J | | | 25 | | | TB0218Y | A006 | BJ | | 050-099, 275-299 |
| 04G | 24 | | PK | | 5-0 | 32-09-11 | D04672J | | | 25 | | | TB0218Y | A006 | BJ | | 150-199 |
| 04H | 24 | | PK | | 6-0 | 32-09-13 | D05832J | | | 27 | | | TB0076Z | | 7 | BJ | ALL |
| 04J | 20 | | PA | | 2-0 | 32-09-11 | D10342 | | | 1 | | | GDX0007 | D.. | 2 | | ALL |
| 04K | 22 | | PA | | 7-0 | 52-11-12 | D02886 | | | B1 | | | D04802J | | 25 | | 050-099, 150-199 |
| 04K | 20 | | PA | | 7-0 | 52-11-12 | D02886 | | | B1 | | | D04802J | | 25 | | 275-299 |
| 04L | 22 | | PA | | 6-0 | 52-11-12 | D02886 | | | B2 | | | D00578 | A3 | | | 050-099 |
| 04L | 22 | | PA | | 2-0 | 52-11-12 | D02886 | | | B2 | | | D00578 | A3 | | | 150-199 |
| 04L | 20 | | PA | | 2-0 | 52-11-12 | D02886 | | | B2 | | | D00578 | A3 | | | 275-299 |
| 04M | 20 | | PA | | 5-0 | 30-21-11 | D10160 | | | X2 | | | GDX0009 | D.. | 2 | | ALL |
| 04Q | 24 | | PK | | 3-0 | 73-21-14 | D05306J | | | 48 | | | D04904J | | 31 | | 050-099, 150-199, 277-299 |
| 04R | 24 | | PK | | 5-0 | 24-51-71 | D03512 | | | A2 | | | TB0216Y | C002 | BJ | | ALL |
| 04S | 22 | | PA | | 3-0 | 27-09-13 | D05433J | | | 41 | | | D05315J | | 1 | | ALL |
| 04T | 22 | | PA | | 3-0 | 27-09-13 | D05433J | | | 42 | | | D05315J | | 2 | | ALL |
| 04U | 22 | | PQ | CA | 5-0 | 32-41-11 | D05658J | | | 34 | | | TB0302X | A006 | BJ | | ALL |
| 04UZ | | | | CA | 0-0 | 32-41-11 | D05658J | | DED | | | | TB0302X | DED | | | ALL |
| 04V | 22 | | PA | | 7-0 | 76-11-11 | D05832J | | | 32 | | | D11752 | | B1 | | 050-099, 155-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 12

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 04V | 20 | PA | | | 7-0 | 76-11-11 | D05832J | | 32 | | D11752 | B1 | | | 150-154 |
| 04W | 24 | PK | | | 5-0 | 24-51-61 | D01388 | | C2 | | D04662J | 31 | | | ALL |
| 04X | 20 | PA | | | 3-0 | 24-51-61 | D01388 | | C1 | | GDX0005 | D.. | 2 | | ALL |
| 04Y | 24 | PK | | | 5-0 | 24-51-71 | D05060J | | 4 | | TB0216Y | A005 | BJ | | ALL |
| 04Z | 22 | PQ | DK | | 5-0 | 74-31-11 | D05306J | | 3 | | D10160 | B2 | | | ALL |
| 04ZZ | | | DK | | 0-0 | 74-31-11 | D05306J | | DED | | D10160 | DED | | | ALL |
| 057 | 24 | PK | | | 5-0 | 21-58-14 | D04904J | | 4 | | TB0218Y | A010 | BJ | | ALL |
| 058 | 24 | PV | FA | | 5-0 | 21-58-14 | D04802J | | 24 | | TB0220X | C010 | BJ | | 050-099, 150-199 |
| 058 | 24 | PV | FA | | 10-0 | 21-58-14 | D04802J | | 24 | | TB0220X | C010 | BJ | | 275-299 |
| 058Z | | | FA | | 0-0 | 21-58-14 | D04802J | | DED | | TB0220X | DED | | | ALL |
| 05A | 22 | PQ | DJ | | 5-0 | 74-31-11 | TB0222X | | B002 | BJ | D10160 | B1 | | * | ALL |
| 05AZ | | | DJ | | 0-0 | 74-31-11 | TB0222X | | DED | | D10160 | DED | | | ALL |
| 05B | 24 | PK | | | 5-0 | 24-51-71 | D05060J | | 2 | | TB0216Y | C002 | BJ | | ALL |
| 05C | 24 | PK | | | 5-0 | 24-51-71 | D05060J | | 3 | | TB0272X | A001 | BJ | | ALL |
| 05D | 24 | PK | | | 5-0 | 24-51-71 | D05060J | | 1 | | TB0218Y | A008 | BJ | | ALL |
| 05E | 24 | PK | | | 5-0 | 24-51-71 | D03512 | | A1 | | TB0272X | B002 | BJ | | ALL |
| 05F | 24 | PV | CF | | 5-0 | 28-25-11 | D01388 | | A1 | | TB0272X | D002 | BJ | | ALL |
| 05FZ | | | CF | | 0-0 | 28-25-11 | D01388 | | DED | | TB0272X | DED | | | ALL |
| 05G | 24 | PV | CG | | 5-0 | 28-25-11 | D01388 | | A2 | | TB0272X | A003 | BJ | | ALL |
| 05GZ | | | CG | | 0-0 | 28-25-11 | D01388 | | DED | | TB0272X | DED | | | ALL |
| 05H | 24 | PK | | | 7-0 | 32-09-11 | D10342 | | 12 | | TB0074Z | 5 | BJ | | ALL |
| 05J | 24 | PK | | | 3-0 | 32-09-11 | D10342 | | 6 | | TB0076Z | 8 | BJ | | 050-099, 275-299 |
| 05J | 24 | PK | | | 4-0 | 32-09-11 | D10342 | | 6 | | TB0076Z | 8 | BJ | | 150-199 |
| 05K | 22 | PA | | | 3-0 | 28-22-21 | D05832J | | 24 | | D05360J | 46 | | | ALL |
| 05M | 22 | PA | | | 4-0 | 32-42-11 | D05658J | | 7 | | TB0272D | C041 | 2 | | ALL |
| 05P | 24 | PK | | | 5-0 | 32-42-11 | D04906J | | 15 | | TB0302X | C007 | BJ | | ALL |
| 05Q | 24 | PK | | | 4-0 | 32-42-11 | D04906J | | 16 | | TB0272X | C003 | BJ | | ALL |
| 05R | 24 | PK | | | 4-0 | 32-42-11 | D04906J | | 17 | | TB0272X | D003 | BJ | | ALL |
| 05S | 24 | PK | | | 4-0 | 32-42-11 | D04906J | | 18 | | TB0272X | A004 | BJ | | ALL |
| 05T | 24 | PK | | | 4-0 | 32-42-11 | D04906J | | 19 | | TB0272X | B004 | BJ | | ALL |
| 05U | 24 | PK | | | 4-0 | 32-42-11 | D04906J | | 20 | | TB0272X | C004 | BJ | | ALL |
| 05V | 24 | PK | | | 4-0 | 32-42-11 | D04906J | | 7 | | TB0272X | D004 | BJ | | ALL |
| 05X | 24 | PK | | | 3-0 | 73-33-11 | D05306J | | 51 | | D05360J | 48 | | | 050-099 |
| 05X | 24 | PK | | | 3-0 | 73-33-11 | D05360J | | 48 | | D05306J | 51 | BJ | | 150-199, 275-278 |
| 05X | 24 | PK | | | 3-0 | 73-33-11 | D05360J | | 48 | | D05306J | 51 | | | 280-299 |
| 05Y | 24 | PK | | | 3-0 | 73-33-11 | D05306J | | 52 | | D05308J | 15 | | | 050-099 |
| 05Y | 24 | PK | | | 3-0 | 73-33-11 | D05308J | | 15 | | D05306J | 52 | | | 150-199, 275-278 |
| 05Y | 24 | PK | | | 5-0 | 73-33-11 | D05308J | | 15 | | D05306J | 52 | | | 280-299 |
| 061 | 22 | PA | | | 4-0 | 52-11-12 | TB0220Y | | C020 | BJ | D00578 | A1 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 13

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | | |
| 061 | 20 | | PA | | 4-0 | 52-11-12 | TB0220Y | C020 | | BJ | | | | D00578 | A1 | | | 275-299 |
| 063 | 20 | | PA | | 3-0 | 52-11-12 | GDX0006 | D.. | 2 | | | | | D00578 | X2 | | | 050-099, 275-299 |
| 063 | 20 | | PA | | 2-0 | 52-11-12 | GDX0006 | D.. | 2 | | | | | D00578 | X2 | | | 150-199 |
| 064 | 22 | | PA | | 4-0 | 52-11-12 | TB0220X | B016 | | BJ | | | | D00578 | A2 | | | 050-099, 150-199 |
| 064 | 20 | | PA | | 4-0 | 52-11-12 | TB0220X | B016 | | BJ | | | | D00578 | A2 | | | 275-299 |
| 065 | 22 | | PA | | 4-0 | 52-11-12 | TB0220Y | C020 | | BJ | | | | D00578 | X1 | | | ALL |
| 06S | 12 | | PA | | 5-0 | 28-22-12 | D05894J | 20 | | | | | | K00329 | A2 | D | | ALL |
| 06T | 12 | | PA | | 5-0 | 28-22-12 | D05894J | 22 | | | | | | K00329 | B2 | D | | ALL |
| 06U | 12 | | PA | | 5-0 | 28-22-12 | D05894J | 24 | | | | | | K00329 | C2 | D | | ALL |
| 071 | 24 | | PK | | 7-0 | 33-16-14 | TB0076Y | C003 | | BJ | | | | D04672J | 49 | | | ALL |
| 072 | 24 | | PK | | 7-0 | 33-16-14 | TB0076Y | C003 | | BJ | | | | D03554 | 7 | | | ALL |
| 073 | 24 | | PK | | 7-0 | 33-16-14 | TB0076Y | C003 | | BJ | | | | D03516 | 7 | | | ALL |
| 074 | 24 | | PK | | 6-0 | 33-16-14 | D03554 | 8 | | | | | | TB0220X | C016 | BJ | | 050-099, 275-299 |
| 074 | 24 | | PK | | 4-0 | 33-16-14 | D03554 | 8 | | | | | | TB0220X | C016 | BJ | | 150-199 |
| 075 | 24 | | PK | | 6-0 | 33-16-14 | D03516 | 8 | | | | | | TB0220X | D016 | BJ | | 050-099, 275-299 |
| 075 | 24 | | PK | | 4-0 | 33-16-14 | D03516 | 8 | | | | | | TB0220X | D016 | BJ | | 150-199 |
| 077 | 24 | | PK | | 6-0 | 34-55-11 | D00598 | 10 | | | | | | D05433J | 36 | | | 050-099, 275-299 |
| 077 | 24 | | PK | | 7-0 | 34-55-11 | D00598 | 10 | | | | | | D05433J | 36 | | | 150-199 |
| 078 | 20 | | PA | | 3-0 | 34-55-11 | D00598 | 11 | | | | | | GDX0007 | D.. | 2 | | ALL |
| 079 | 24 | | PK | | 6-0 | 34-46-12 | D03516 | 5 | | | | | | D05433J | 3 | | | ALL |
| 07A | 16 | | PA | | 5-0 | 27-32-31 | D04338J | 27 | FM | | | | | TB0252G | 3 | 2 | | ALL |
| 07B | 20 | | PA | | 5-0 | 27-32-31 | D10456 | X1 | | | | | | TB0252G | 3 | 2 | | ALL |
| 07C | 20 | | PA | | 5-0 | 27-32-31 | D10456 | A2 | | | | | | TB0252G | 3 | 2 | | ALL |
| 07D | 16 | | PA | | 5-0 | 27-32-31 | D10458 | A2 | | | | | | TB0252G | 3 | 2 | | ALL |
| 07E | 16 | | PA | | 5-0 | 27-32-31 | D10458 | A3 | | | | | | D05433J | 51 | FL | | ALL |
| 07F | 16 | | PA | | 5-0 | 27-32-31 | D10458 | A1 | | | | | | D05433J | 55 | FL | | ALL |
| 07G | 20 | | PA | | 5-0 | 27-32-31 | D10458 | X2 | | | | | | D05433J | 34 | | | ALL |
| 07H | 20 | | PA | | 4-0 | 27-32-31 | D10458 | X1 | | | | | | D10456 | A1 | | | ALL |
| 07J | 20 | | PA | | 5-0 | 27-32-31 | D10456 | X2 | | | | | | TB0216X | A003 | BJ | | 050-099, 275-299 |
| 07J | 20 | | PA | | 4-0 | 27-32-31 | D10456 | X2 | | | | | | TB0216X | A003 | BJ | | 150-199 |
| 07N | 24 | | PK | | 5-0 | 34-61-15 | D01723 | X1 | | | | | | D05497J | 13 | | | ALL |
| 07P | 20 | | PA | | 5-0 | 34-61-15 | D01723 | X2 | | | | | | D05497J | 1 | | | 050-099, 150-199 |
| 07P | 20 | | PA | | 6-0 | 34-61-15 | D01723 | X2 | | | | | | D05497J | 1 | | | 275-299 |
| 080 | 20 | | PA | | 3-0 | 34-46-12 | D03516 | 3 | | | | | | GDX0004 | S.. | 2 | | ALL |
| 089 | 24 | | PK | | 5-0 | 21-58-16 | D02910 | B2 | | | | | | TB0222X | C013 | BJ | | ALL |
| 08A | 24 | | PV | FB | 7-0 | 32-09-11 | M01161 | A | | C | | | | TB0076Y | A003 | BJ | | ALL |
| 08AZ | | | | FB | 0-0 | 32-09-11 | M01161 | DED | | | | | | TB0076Y | DED | | | ALL |
| 08B | 24 | | PK | | 7-0 | 32-09-11 | M01162 | A | | C | | | | TB0076Z | 11 | BJ | | 050-099, 275-299 |
| 08B | 24 | | PK | | 6-0 | 32-09-11 | M01162 | A | | C | | | | TB0076Z | 11 | BJ | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 14

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 08D | 20 | PA | | | 2-0 | 73-21-19 | D02910 | | | | D3 | | | | 050-099 |
| 08D | 20 | PA | | | 3-0 | 73-21-19 | D02910 | | | | D3 | | | | 150-199, 275-299 |
| 08E | 22 | PA | | | 5-0 | 73-21-19 | D03612 | | | | 3 | | | | ALL |
| 08F | 22 | PA | | | 6-0 | 73-21-19 | D03622 | | | | X2 | | | | 050-099, 150-199 |
| 08F | 22 | PA | | | 10-0 | 73-21-19 | D03622 | | | | X2 | | | | 275-299 |
| 08G | 22 | PA | | | 10-0 | 73-21-19 | TB0258D | | A006 | 2 | | | | | 275-299 |
| 08H | 24 | PK | | | 5-0 | 31-31-13 | D01793 | | | | 3 | | | | ALL |
| 08I | 24 | PK | | | 5-0 | 31-31-13 | D01793 | | | | 7 | | | | ALL |
| 08J | 24 | PK | | | 3-0 | 31-31-13 | D01793 | | | | 8 | | | | ALL |
| 08K | 20 | PA | | | 5-0 | 31-31-13 | D01793 | | | | 6 | | | | ALL |
| 08M | 22 | PA | | | 6-0 | 29-21-32 | D00598 | | | | 8 | | | | ALL |
| 08N | 22 | PA | | | 6-0 | 29-21-32 | D00598 | | | | 7 | | | | ALL |
| 08P | 24 | PK | | | 6-0 | 32-09-11 | D11798 | | | | 6 | | | | 050-099, 150-199, 276-299 |
| 08P | 24 | PK | | | 4-0 | 32-09-11 | D11798 | | | | 6 | | | | 275 |
| 08R | 24 | PK | | | 4-0 | 32-09-11 | D11798 | | | | 12 | | | | ALL |
| 090 | 20 | PA | | | 3-0 | 21-58-16 | D02910 | | | | B3 | | | | ALL |
| 091 | 18 | PA | | | 7-0 | 33-42-11 | D05714J | | | | 1 | | | | 050-099, 150-199 |
| 091 | 18 | PA | | | 6-0 | 33-42-11 | D05714J | | | | 1 | | | | 275-299 |
| 092 | 18 | PA | | | 7-0 | 33-42-11 | D05714J | | | | 2 | | | | 050-099, 150-199 |
| 092 | 18 | PA | | | 6-0 | 33-42-11 | D05714J | | | | 2 | | | | 275-299 |
| 093 | 18 | PA | | | 5-0 | 33-42-11 | D04932J | | 51 | DK | | | | | 050-099 |
| 093 | 16 | PA | | | 6-0 | 33-42-11 | D04932J | | 15 | FM | | | | | 150-199 |
| 093 | 16 | PA | | | 5-0 | 33-42-11 | D04932J | | 15 | FM | | | | | 275-299 |
| 094 | 20 | PA | | | 5-0 | 33-42-11 | D04932J | | 52 | | | | | | 050-099 |
| 094 | 16 | PA | | | 6-0 | 33-42-11 | D04932J | | 52 | FM | | | | | 150-199 |
| 094 | 16 | PA | | | 5-0 | 33-42-11 | D04932J | | 52 | FM | | | | | 275-299 |
| 098 | 20 | PA | | | 7-0 | 33-42-11 | D04672J | | 60 | | | | | | ALL |
| 09A | 24 | PK | | | 5-0 | 21-44-21 | D05658J | | | | 8 | | | | ALL |
| 09B | 24 | PK | | | 4-0 | 36-11-41 | D04662J | | | | 34 | | | | ALL |
| 09C | 24 | PK | | | 6-0 | 36-11-41 | D04662J | | | | 32 | | | | ALL |
| 09D | 24 | PK | | | 6-0 | 36-11-41 | D04662J | | | | 33 | | | | ALL |
| 09E | 22 | PA | | | 5-0 | 31-31-11 | D05433J | | | | 18 | | | | ALL |
| 09G | 24 | PK | | | 8-0 | 32-09-11 | D10342 | | | | 2 | | | | ALL |
| 09H | 24 | PK | | | 2-0 | 32-09-11 | D01612 | | | | B3 | | | | ALL |
| 09I | 20 | PA | | | 2-0 | 32-09-11 | D01612 | | | | B2 | | | | ALL |
| 09K | 24 | PK | | | 5-0 | 21-45-21 | D10738 | | | | X1 | | | | 050-099 |
| 09K | 24 | VA | | | 9-0 | 21-45-21 | D10738 | | | | X1 | | | | 150-199 |
| 09K | 24 | PK | | | 13-0 | 21-45-21 | D10738 | | | | X1 | | | | 275-277 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 15

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 09K | 24 | | PK | 6-0 | 21-45-21 | D10738 | | X1 | | | | TB0216Y | C012 | BJ | | 278-299 |
| 09L | 22 | | PA | 5-0 | 21-45-21 | D10738 | | A1 | | | | D04662J | 51 | | | 050-099, 150-156, 162-166, 275-276 |
| 09L | 20 | | PA | 5-0 | 21-45-21 | D10738 | | A1 | | | | D04662J | 51 | | | 157, 167-199, 277-299 |
| 09M | 22 | | PA | 5-0 | 21-45-21 | D10738 | | B1 | | | | D04662J | 52 | | | 050-099, 150-156, 162-166, 275-276 |
| 09M | 20 | | PA | 5-0 | 21-45-21 | D10738 | | B1 | | | | D04662J | 52 | | | 157, 167-199, 277-299 |
| 09N | 24 | | PK | 2-0 | 21-45-21 | D10738 | | X2 | | | | D03512 | D2 | | | 050-099 |
| 09N | 24 | | VA | 12-0 | 21-45-21 | D10738 | | X2 | | | | TB0074Y | C014 | BJ | | 150-199 |
| 09N | 24 | | PK | 12-0 | 21-45-21 | D10738 | | X2 | | | | TB0074Y | C014 | BJ | | 275-277 |
| 09N | 24 | | PK | 8-0 | 21-45-21 | D10738 | | X2 | | | | TB0074Y | C014 | BJ | | 278-299 |
| 09P | 22 | | PA | 5-0 | 21-45-21 | D10738 | | A2 | | | | TB0272X | A013 | BJ | | 050-099, 150-156, 162-166, 275-276 |
| 09P | 20 | | PA | 5-0 | 21-45-21 | D10738 | | A2 | | | | TB0272X | A013 | BJ | | 157, 167-199, 277-299 |
| 09Q | 22 | | PA | 5-0 | 21-45-21 | D10738 | | B2 | | | | TB0272X | B013 | BJ | | 050-099, 150-156, 162-166, 275-276 |
| 09Q | 20 | | PA | 5-0 | 21-45-21 | D10738 | | B2 | | | | TB0272X | B013 | BJ | | 157, 167-199, 277-299 |
| 09Y | 24 | | PK | 3-0 | 21-45-21 | D03512 | | D1 | | | | TB0260D | A007 | 2 | | ALL |
| 100 | 20 | | PQ | 4-0 | 78-34-11 | TB0076Z | | 10 | BJ | | | D03536 | C1 | | | 050-099, 150-156, 162-166, 275-276 |
| 100 | 20 | | PQ | 5-0 | 78-34-11 | TB0076Z | | 10 | BJ | | | D03536 | C1 | | | 157, 167-199, 277-299 |
| 100Z | | | HL | 0-0 | 78-34-11 | TB0076Z | | | | HJ | | D03536 | DED | | | ALL |
| 102 | 24 | | PK | 7-0 | 32-09-11 | D04672J | | 19 | | | | TB0076Z | 7 | BJ | | ALL |
| 103 | 24 | | PK | 3-0 | 32-09-11 | D03614 | | 6 | | | | TB0074Z | 10 | BJ | | ALL |
| 104 | 24 | | PK | 6-0 | 32-09-11 | D03614 | | 12 | | | | TB0076Z | 9 | BJ | | ALL |
| 105 | 24 | | PK | 6-0 | 32-09-11 | D03554 | | 12 | | | | TB0076Z | 9 | BJ | | ALL |
| 106 | 24 | | PK | 8-0 | 32-09-11 | D03554 | | 6 | | | | TB0074Z | 10 | BJ | | ALL |
| 107 | 16 | | PA | 5-0 | 33-45-11 | D05312J | | 13 | FM | | | TB0302F | A010 | 2 | | ALL |
| 108 | 16 | | PA | 5-0 | 33-45-11 | D05312J | | 14 | FM | | | TB0302F | C010 | 2 | | ALL |
| 109 | 24 | | PK | 6-0 | 32-09-11 | D03516 | | 12 | | | | TB0076Z | 9 | BJ | | ALL |
| 10A | 24 | | PK | 8-0 | 21-45-21 | TB0074Y | | C013 | BJ | | | TB0260D | C007 | 2 | | ALL |
| 10B | 24 | | PK | 6-0 | 21-45-21 | TB0260D | | A007 | 2 | | | D04662J | 37 | | | ALL |
| 10D | 22 | | PA | 1-0 | SPARE | TB0250Y | | A002 | BJ | | | TB0250Y | C002 | BJ | | 050-099 |
| 10D | 22 | | PA | 2-0 | 30-21-11 | TB0250Y | | C002 | BJ | | | TB0250Y | A002 | BJ | | 275-299 |
| 10E | 24 | | PK | 7-0 | 21-25-11 | TB0074Y | | C013 | BJ | | | D04672J | 43 | | | ALL |
| 10Q | 24 | | PK | 6-0 | 31-31-21 | D05431J | | 22 | | | | D02914 | 3 | | | ALL |
| 10R | 24 | | PK | 6-0 | 31-31-21 | D05431J | | 24 | | | | D02914 | 5 | | | ALL |
| 110 | 24 | | PK | 6-0 | 32-09-11 | D03516 | | 6 | | | | TB0076Z | 7 | BJ | | ALL |
| 113 | 24 | | PK | 3-0 | 32-09-11 | TB0076Z | | 8 | BJ | | | TB0076Z | 7 | BJ | | 050-099, 277-278 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 16

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 113 | 24 | | PK | | 2-0 | 32-09-11 | TB0076Z | 8 | BJ | | TB0076Z | 7 | BJ | | 150-199 |
| 113 | 24 | | PK | | 3-0 | 32-09-11 | TB0076Z | 8 | BJ | | TB0076Y | A004 | BJ | | 275-276 |
| 113 | 24 | | PK | | 1-0 | 32-09-11 | TB0076Z | 8 | BJ | | TB0076Z | 7 | BJ | | 280-299 |
| 116 | 24 | | PK | | 7-0 | 32-09-11 | TB0074Z | 10 | BJ | | TB0076Y | A004 | BJ | | ALL |
| 117 | 24 | | PK | | 6-0 | 32-09-11 | D03610 | 6 | | | TB0076Z | 7 | BJ | | 050-099, 275-299 |
| 117 | 24 | | PK | | 7-0 | 32-09-11 | D03610 | 6 | | | TB0076Z | 7 | BJ | | 150-199 |
| 118 | 24 | | PK | | 6-0 | 32-09-11 | D03610 | 12 | | | TB0076Z | 9 | BJ | | 050-099, 275-299 |
| 118 | 24 | | PK | | 7-0 | 32-09-11 | D03610 | 12 | | | TB0076Z | 9 | BJ | | 150-199 |
| 119 | 24 | | PK | | 6-0 | 32-09-11 | TB0218Y | A006 | BJ | | D02914 | 12 | | | 050-099, 275-299 |
| 119 | 24 | | PK | | 5-0 | 32-09-11 | TB0218Y | A006 | BJ | | D02914 | 12 | | | 150-199 |
| 11A | 22 | | PA | | 2-0 | 73-21-11 | D11752 | | Y2 | | GD00003 | D.. | 2 | | 050-099 |
| 11A | 22 | | PA | | 3-0 | 73-21-11 | D11752 | | Y2 | | GD00003 | D.. | 2 | | 150-199, 275-299 |
| 11B | 20 | | UA | | 2-0 | 73-21-11 | D11752 | | | FB | GD00003 | S.. | 2 | | 050-099 |
| 11B | 20 | | UA | | 3-0 | 73-21-11 | D11752 | | | F2 | GD00003 | S.. | 2 | | 150-154, 162-199 |
| 11B | 20 | | UA | | 5-0 | 73-21-11 | D11752 | | | F2 | GD00003 | S.. | 2 | | 155-157 |
| 11B | 20 | | UA | | 4-0 | 73-21-11 | D11752 | | | F2 | GD00003 | S.. | 2 | | 275-299 |
| 11C | 24 | | PV | SF | 4-0 | 73-21-11 | D11752 | A1 | | | D06582J | 17 | | | 050-099 |
| 11C | 24 | | PV | EU | 7-0 | 73-21-11 | D11752 | A1 | | | D06582J | 17 | | | 150-154, 162-199, 275-299 |
| 11C | 24 | | PV | EU | 5-0 | 73-21-11 | D11752 | A1 | | | D06582J | 17 | | | 155-157 |
| 11CZ | | | | SF | 0-0 | 73-21-11 | D11752 | | | FB | D06582J | | | FC | 050-099 |
| 11CZ | | | | EU | 0-0 | 73-21-11 | D11752 | | | F2 | D06582J | | | F3 | 150-199, 275-299 |
| 11D | 24 | | PV | SP | 4-0 | 73-21-11 | D11752 | A2 | | | D06582J | 18 | | | 050-099 |
| 11D | 24 | | PV | EZ | 7-0 | 73-21-11 | D11752 | A2 | | | D06582J | 18 | | | 150-154, 162-199, 275-299 |
| 11D | 24 | | PV | EZ | 5-0 | 73-21-11 | D11752 | A2 | | | D06582J | 18 | | | 155-157 |
| 11DZ | | | | SP | 0-0 | 73-21-11 | D11752 | | | FB | D06582J | | | FC | 050-099 |
| 11DZ | | | | EZ | 0-0 | 73-21-11 | D11752 | | | F2 | D06582J | | | F3 | 150-199, 275-299 |
| 11E | 24 | | PK | | 4-0 | 73-21-11 | D11752 | X1 | | | TB0216Z | 14 | BJ | | 050-099, 150-154, 275-276 |
| 11E | 24 | | PK | | 10-0 | 73-21-11 | D11752 | X1 | | | TB0080Z | 4 | BJ | | 155-199, 277-299 |
| 11F | 22 | | PA | | 2-0 | 73-21-11 | D11752 | X2 | | | GD00003 | D.. | 2 | | 050-099 |
| 11F | 22 | | PA | | 3-0 | 73-21-11 | D11752 | X2 | | | GD00003 | D.. | 2 | | 150-199, 275-299 |
| 11G | 24 | | PK | | 4-0 | 73-21-11 | D11750 | Y1 | | | TB0218Y | C017 | BJ | | 050-099, 150-199, 277-299 |
| 11G | 24 | | PK | | 4-0 | 73-21-11 | D11750 | Y1 | | | TB0218X | D004 | BJ | | 275-276 |
| 11H | 22 | | PA | | 2-0 | 73-21-11 | D11750 | Y2 | | | GD00003 | D.. | 2 | | 050-099 |
| 11H | 22 | | PA | | 3-0 | 73-21-11 | D11750 | Y2 | | | GD00003 | D.. | 2 | | 150-199, 275-299 |
| 11J | 20 | | UA | | 2-0 | 73-21-11 | D11750 | | | FD | GD00003 | S.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11
Section W0170
Page 17
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 11J | 20 | | UA | | 3-0 | 73-21-11 | D11750 | | | F0 | GDX0003 | S.. | 2 | | 150-154, 162-199 |
| 11J | 20 | | UA | | 5-0 | 73-21-11 | D11750 | | | F0 | GDX0003 | S.. | 2 | | 155-157 |
| 11J | 20 | | UA | | 4-0 | 73-21-11 | D11750 | | | F0 | GDX0003 | S.. | 2 | | 275-299 |
| 11K | 24 | | PV | AN | 5-0 | 73-21-11 | D11750 | | A1 | | D05832J | | 34 | | 050-099 |
| 11K | 24 | | PV | ET | 7-0 | 73-21-11 | D11750 | | A1 | | D05832J | | 34 | | 150-154, 162-199 |
| 11K | 24 | | PV | ET | 5-0 | 73-21-11 | D11750 | | A1 | | D05832J | | 34 | | 155-157 |
| 11K | 24 | | PV | ET | 6-0 | 73-21-11 | D11750 | | A1 | | TB0218X | B004 | BJ | | 275-276 |
| 11K | 24 | | PV | ET | 6-0 | 73-21-11 | D11750 | | A1 | | D05832J | | 34 | | 277-299 |
| 11KZ | | | | AN | 0-0 | 73-21-11 | D11750 | | | FD | D05832J | | | FA | 050-099 |
| 11KZ | | | | ET | 0-0 | 73-21-11 | D11750 | | | F0 | D05832J | | | F1 | 150-199, 277-299 |
| 11KZ | | | | ET | 0-0 | 73-21-11 | D11750 | | | F0 | TB0218X | A004 | BJ | | 275-276 |
| 11L | 24 | | PV | AE | 4-0 | 73-21-11 | D11750 | | A2 | | D05832J | | 33 | | 050-099 |
| 11L | 24 | | PV | ES | 7-0 | 73-21-11 | D11750 | | A2 | | D05832J | | 33 | | 150-154, 162-199, 275-299 |
| 11L | 24 | | PV | ES | 5-0 | 73-21-11 | D11750 | | A2 | | D05832J | | 33 | | 155-157 |
| 11LZ | | | | AE | 0-0 | 73-21-11 | D11750 | | | FD | D05832J | | | FA | 050-099 |
| 11LZ | | | | ES | 0-0 | 73-21-11 | D11750 | | | F0 | D05832J | | | F1 | 150-199, 275-299 |
| 11M | 24 | | PK | | 4-0 | 73-21-11 | D11750 | | X1 | | TB0218Y | A017 | BJ | | 050-099, 150-199, 277-299 |
| 11M | 24 | | PK | | 4-0 | 73-21-11 | D11750 | | X1 | | TB0218X | C004 | BJ | | 275-276 |
| 11N | 22 | | PA | | 2-0 | 73-21-11 | D11750 | | X2 | | GDX0003 | D.. | 2 | | 050-099 |
| 11N | 22 | | PA | | 4-0 | 73-21-11 | D11750 | | X2 | | GDX0003 | D.. | 2 | | 150-157, 275-299 |
| 11N | 22 | | PA | | 3-0 | 73-21-11 | D11750 | | X2 | | GDX0003 | D.. | 2 | | 162-199 |
| 11P | 24 | | PV | FG | 6-0 | 73-21-11 | D05832J | | 34 | | TB0218X | B004 | BJ | | 275-276 |
| 11PZ | | | | FG | 0-0 | 73-21-11 | D05832J | | | F1 | TB0218X | A004 | BJ | | 275-276 |
| 11R | 24 | | PK | | 5-0 | 21-61-71 | D13410 | | X1 | | TB0272Z | 17 | BJ | | 050-099 |
| 11R | 24 | | PK | | 4-0 | 21-61-71 | D13410 | | X1 | | TB0272Z | 17 | BJ | | 150-199, 275-299 |
| 11S | 20 | | PA | | 5-0 | 21-61-71 | D13410 | | A2 | | GDX0009 | D.. | 2 | | ALL |
| 11X | 24 | | PK | | 4-0 | 21-61-71 | D13410 | | A3 | | TB0272Y | C031 | BJ | | 050-099 |
| 11X | 24 | | PK | | 7-0 | 21-61-71 | D13410 | | A3 | | TB0302Y | A025 | BJ | | 150-199 |
| 11X | 24 | | PK | | 7-0 | 21-61-71 | D13410 | | A3 | | TB0272Y | C031 | BJ | | 275-299 |
| 11Y | 24 | | PK | | 3-0 | 21-61-71 | D13410 | | A1 | | D13412 | 2 | | | ALL |
| 120 | 24 | | PK | | 6-0 | 78-34-11 | D05300J | | 35 | | TB0076Z | 10 | BJ | | ALL |
| 122 | 24 | | PV | BU | 5-0 | 32-09-11 | D01388 | | X1 | | TB0216Z | 13 | BJ | | ALL |
| 122Z | | | | BU | 0-0 | 32-09-11 | D01388 | | DED | | TB0216Z | DED | | | ALL |
| 123 | 24 | | PK | | 7-0 | 32-09-11 | D03532 | | 12 | | TB0076Z | 9 | BJ | | 050-099 |
| 123 | 24 | | PK | | 6-0 | 32-09-11 | D03532 | | 12 | | TB0076Z | 9 | BJ | | 150-199, 275-299 |
| 124R | 22 | | PH | | 4-0 | 26-18-11 | D04672J | | 31 | | D04904J | 12 | | | ALL |
| 125 | 22 | | PA | | 3-0 | 23-31-12 | D04709J | | 12 | | TB0222X | D010 | BJ | | 050-099, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 18

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|---------|-------------|------------------|------------------|---------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | | |
| 125 | 22 | | PA | | 4-0 | 23-31-12 | TB0222X | D010 | | BJ | | | | 12 | | 150-199 | | |
| 126 | 22 | | PA | | 7-0 | 24-25-11 | D03514 | | 11 | | | | | B007 | BJ | ALL | | |
| 127 | 22 | | PA | | 7-0 | 24-25-11 | D03514 | | 10 | | | | | D007 | BJ | ALL | | |
| 128 | 24 | | PK | | 4-0 | 24-25-13 | D05308J | | 36 | | | | | A008 | BJ | ALL | | |
| 129 | 24 | | PK | | 4-0 | 24-25-13 | D05308J | | 37 | | | | | B008 | BJ | ALL | | |
| 12W | 24 | | PK | | 5-0 | 21-61-71 | D13410 | | X2 | | | | | D05658J | | 050-099 | | |
| 12W | 24 | | PK | | 5-0 | 21-61-71 | D05658J | | 15 | | | | | D13410 | X2 | 150-199, 275-299 | | |
| 12X | 24 | | PK | | 4-0 | 21-61-71 | D05658J | | 14 | | | | | TB0272Y | C031 | BJ | 050-099 | |
| 12X | 24 | | PK | | 5-0 | 21-61-71 | D05658J | | 14 | | | | | TB0302Y | A025 | BJ | 150-199 | |
| 12X | 24 | | PK | | 5-0 | 21-61-71 | D05658J | | 14 | | | | | TB0272Y | C031 | BJ | 275-299 | |
| 12Y | 24 | | PK | | 4-0 | 21-61-71 | D13412 | | 1 | | | | | TB0272Y | C031 | BJ | 050-099 | |
| 12Y | 24 | | PK | | 7-0 | 21-61-71 | D13412 | | 1 | | | | | TB0302Y | A025 | BJ | 150-199 | |
| 12Y | 24 | | PK | | 7-0 | 21-61-71 | D13412 | | 1 | | | | | TB0272Y | C031 | BJ | 275-299 | |
| 130 | 24 | | PK | | 4-0 | 24-25-13 | D05308J | | 38 | | | | | TB0302X | C008 | BJ | ALL | |
| 131 | 24 | | PK | | 4-0 | 24-25-13 | D05308J | | 39 | | | | | TB0302X | D008 | BJ | ALL | |
| 133 | 24 | | PV | AU | 7-0 | 32-09-11 | TB0074Z | | 4 | | BJ | | | D04802J | | 10 | ALL | |
| 133Z | | | | AU | 0-0 | 32-09-11 | D04802J | | | DED | | | | TB0074Z | | DED | ALL | |
| 134 | 24 | | PV | AZ | 9-0 | 32-09-11 | TB0074Z | | 4 | | BJ | | | D10950 | | X2 | ALL | |
| 134Z | | | | AZ | 0-0 | 32-09-11 | D10950 | | | DED | | | | TB0074Z | | DED | ALL | |
| 135 | 24 | | PV | BD | 8-0 | 32-09-11 | TB0216Z | | 13 | | BJ | | | D10950 | | X1 | ALL | |
| 135Z | | | | BD | 0-0 | 32-09-11 | D10950 | | | DED | | | | TB0216Z | | DED | ALL | |
| 137R | 22 | | PH | | 4-0 | 26-18-31 | D04672J | | 35 | | | | | D04932J | | 3 | ALL | |
| 13B | 24 | | PV | K | 3-0 | 73-21-17 | D05832J | | 44 | | | | | D05315J | | 11 | 050-099 | |
| 13B | 24 | | PV | DO | 4-0 | 73-21-17 | D05832J | | 44 | | | | | D05315J | | 11 | 150-199, 275-299 | |
| 13BZ | | | | K | 0-0 | 73-21-17 | D05832J | | | | | FF | | D05315J | | | FL | 050-099 |
| 13BZ | | | | DO | 0-0 | 73-21-17 | D05832J | | 46 | | | | | D05315J | | 10 | 150-199 | |
| 13BZ | | | | DO | 0-0 | 73-21-17 | D05832J | | | | | F4 | | D05315J | | | F5 | 275-299 |
| 13C | 24 | | PV | O | 3-0 | 73-21-17 | D05832J | | 45 | | | | | D05315J | | 12 | 050-099 | |
| 13C | 24 | | PK | | 4-0 | 73-21-17 | D05832J | | 45 | | | | | D05315J | | 12 | 150-199 | |
| 13C | 24 | | PV | FH | 4-0 | 73-21-17 | D05832J | | 45 | | | | | D05315J | | 12 | 275-299 | |
| 13CZ | | | | O | 0-0 | 73-21-17 | D05832J | | | | | FF | | D05315J | | | FL | 050-099 |
| 13CZ | | | | FH | 0-0 | 73-21-17 | D05832J | | | | | F4 | | D05315J | | | F5 | 275-299 |
| 13W | 24 | | PK | | 8-0 | 21-61-71 | D13408 | | X2 | | | | | TB0272Y | C031 | BJ | 050-099 | |
| 13W | 24 | | PK | | 8-0 | 21-61-71 | TB0302Y | | A025 | | BJ | | | D13408 | | X2 | 150-199 | |
| 13W | 24 | | PK | | 8-0 | 21-61-71 | TB0272Y | | C031 | | BJ | | | D13408 | | X2 | 275-299 | |
| 13X | 24 | | PK | | 5-0 | 21-61-71 | D13412 | | 5 | | | | | TB0272Y | A006 | BJ | ALL | |
| 14J | 24 | | PK | | 9-0 | 21-61-51 | D13400 | | X1 | | | | | D04662J | | 19 | 050-099 | |
| 14J | 24 | | PK | | 7-0 | 21-61-51 | D04662J | | 19 | | | | | D13400 | | X1 | 150-199, 275-299 | |
| 14V | 24 | | PK | | 10-0 | 21-61-51 | D13400 | | X2 | | | | | TB0076Y | A005 | BJ | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 19

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|---------------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 14V | 24 | | PK | | 7-0 | 21-61-51 | D04906J | | | | 24 | | | | 150-199, 275-299 |
| 14W | 20 | | PA | | 4-0 | 21-61-51 | D13400 | | | | A1 | | | | 050-099, 150-199 |
| 14W | 20 | | UA | | 4-0 | 21-61-51 | D13400 | | | | A1 | | | | 275-299 |
| 14X | 20 | | PA | | 4-0 | 21-61-51 | D13400 | | | | B1 | | | | 050-099, 150-199 |
| 14X | 20 | | UA | | 4-0 | 21-61-51 | D13400 | | | | B1 | | | | 275-299 |
| 152 | 24 | | PK | | 4-0 | 21-51-11 | D04932J | | | | 17 | | | | 150-199 |
| 152 | 24 | | PK | | 5-0 | 21-51-11 | D04932J | | | | 17 | | | | 275-299 |
| 156 | 22 | | PA | | 5-0 | 31-31-11 | D05433J | | | | 44 | | | | ALL |
| 157 | 24 | | PK | | 4-0 | 21-51-11 | D04672J | | | | 1 | | | | 150-199, 275-299 |
| 158 | 24 | | PK | | 5-0 | 21-51-11 | D04672J | | | | 14 | | | | 150-199 |
| 158 | 24 | | PK | | 4-0 | 21-51-11 | D04672J | | | | 14 | | | | 275-299 |
| 159 | 24 | | PK | | 5-0 | 23-12-11 | D04709J | | | | 8 | | | | 050-099 |
| 159 | 24 | | PK | | 5-0 | 23-12-11 | D02912 | | | | 5 | | | | 150-199, 275-299 |
| 15A | 20 | | PA | | 5-0 | 21-58-11 | D13418 | | | | 2 | | | | ALL |
| 15B | 24 | | PK | | 7-0 | 21-58-11 | D13418 | | | | 3 | | | | ALL |
| 15C | 24 | | PK | | 7-0 | 21-58-11 | D13418 | | | | 5 | | | | 050-099, 150-155, 162-165, 275-276 |
| 15C | 24 | | PK | | 7-0 | 21-58-11 | D13418 | | | | 5 | | | | 156-157, 166-199, 277-299 |
| 15D | 24 | | PK | | 5-0 | 21-58-11 | D13418 | | | | 7 | | | | ALL |
| 15J | 24 | | PK | | 5-0 | 21-58-11 | D04904J | | | | 41 | | | | ALL |
| 15K | 24 | | PK | | 8-0 | 21-58-11 | TB0080D | | | | C012 | 2 | | | ALL |
| 15N | 20 | | PA | | 4-0 | 21-61-71 | D13412 | | | | 6 | | | | 050-099 |
| 15N | 20 | | PA | | 5-0 | 21-61-71 | D13412 | | | | 6 | | | | 150-199, 275-299 |
| 15P | 24 | | PK | | 5-0 | 21-61-71 | D13412 | | | | 7 | | | | 050-099 |
| 15P | 24 | | PK | | 4-0 | 21-61-71 | D13412 | | | | 7 | | | | 150-199 |
| 15P | 24 | | PK | | 4-0 | 21-61-71 | D13412 | | | | 7 | | | | 275-299 |
| 15R | 24 | | PK | | 5-0 | 21-61-71 | D13412 | | | | 3 | | | | 050-099 |
| 15R | 24 | | PK | | 4-0 | 21-61-71 | D13412 | | | | 3 | | | | 150-199 |
| 15R | 24 | | PK | | 4-0 | 21-61-71 | D13412 | | | | 3 | | | | 275-299 |
| 15S | 24 | | PK | | 2-0 | 21-61-71 | TB0272D | | | | A037 | 2 | | | 050-099, 275-299 |
| 15S | 24 | | PK | | 2-0 | 21-61-71 | TB0272D | | | | A020 | 2 | | | 150-199 |
| 15U | 24 | | PK | | 5-0 | 21-61-71 | D05433J | | | | 40 | | | | ALL |
| 15V | 24 | | PK | | 8-0 | 21-61-71 | D13410 | | | | B2 | | | | 050-099 |
| 15V | 24 | | PK | | 5-0 | 21-61-71 | D05433J | | | | 45 | | | | 150-199, 275-299 |
| 15W | 24 | | PK | | 8-0 | 21-61-71 | D13410 | | | | B1 | | | | 050-099 |
| 15W | 24 | | PK | | 5-0 | 21-61-71 | D13410 | | | | B1 | | | | 150-199, 275-299 |
| 15Y | 24 | | PK | | 8-0 | 21-61-71 | D13408 | | | | C1 | | | | ALL |
| 160 | 22 | | PA | | 5-0 | 31-31-11 | D05433J | | | | 43 | | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 20

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|---|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | | |
| 161 | 20 | PA | | | 3-0 | 23-12-11 | D02912 | | | | 4 | | | GDX0004 | D.. | 2 | | ALL |
| 162 | 22 | PA | | | 12-0 | 74-31-11 | D05308J | | | | 13 | | | D10160 | D1 | | * | 050-099 |
| 162 | 22 | PA | | | 4-0 | 74-31-11 | D05308J | | | | 13 | | | D10160 | D1 | | * | 150-199, 275-299 |
| 169 | 24 | PK | | | 6-0 | 21-58-13 | D04672J | | | | 9 | | | D03586 | A2 | | | ALL |
| 16A | 24 | PK | | | 8-0 | 21-61-71 | D13408 | | | | C2 | | | D05497J | 23 | | | 050-099 |
| 16A | 22 | PA | | | 7-0 | 21-61-71 | D13408 | | | | C2 | | | D05497J | 23 | | | 150-199 |
| 16A | 24 | PK | | | 7-0 | 21-61-71 | D13408 | | | | C2 | | | D05497J | 23 | | | 275-299 |
| 16B | 24 | PK | | | 8-0 | 21-61-71 | D13408 | | | | B2 | | | D05497J | 24 | | | 050-099 |
| 16B | 24 | PK | | | 7-0 | 21-61-71 | D13408 | | | | B2 | | | D05497J | 24 | | | 150-199, 275-299 |
| 16C | 24 | PK | | | 2-0 | 21-61-71 | TB0272Z | | | | 17 | BJ | | TB0272D | C037 | 2 | | 050-099 |
| 16C | 24 | PK | | | 2-0 | 21-61-71 | TB0272D | | | | C020 | 2 | | TB0272Z | 17 | BJ | | 150-199 |
| 16C | 24 | PK | | | 2-0 | 21-61-71 | TB0272D | | | | C037 | 2 | | TB0272Z | 17 | BJ | | 275-299 |
| 16D | 24 | PK | | | 2-0 | 21-61-61 | TB0272Z | | | | 17 | BJ | | TB0272D | C033 | 2 | | 050-099 |
| 16D | 24 | PK | | | 2-0 | 21-61-61 | TB0272D | | | | C033 | 2 | | TB0272Z | 17 | BJ | | 150-199, 275-299 |
| 16H | 24 | PK | | | 5-0 | 21-61-61 | D13404 | | | | X1 | | | TB0272Z | 17 | BJ | | 050-099 |
| 16H | 24 | PK | | | 4-0 | 21-61-61 | D13404 | | | | X1 | | | TB0272Z | 17 | BJ | | 150-199, 275-299 |
| 16J | 20 | PA | | | 4-0 | 21-61-61 | D13404 | | | | A2 | | | GDX0009 | D.. | 2 | | 050-099 |
| 16J | 20 | PA | | | 5-0 | 21-61-61 | D13404 | | | | A2 | | | GDX0009 | D.. | 2 | | 150-199, 275-299 |
| 16L | 24 | PK | | | 4-0 | 21-61-61 | D13404 | | | | A1 | | | D13406 | 2 | | | 050-099 |
| 16L | 24 | PK | | | 3-0 | 21-61-61 | D13404 | | | | A1 | | | D13406 | 2 | | | 150-199, 275-299 |
| 16M | 24 | PK | | | 5-0 | 21-61-61 | D13404 | | | | A3 | | | TB0272Y | A031 | BJ | | 050-099 |
| 16M | 24 | PK | | | 4-0 | 21-61-61 | D13404 | | | | A3 | | | TB0272Y | A031 | BJ | | 150-199, 275-299 |
| 16N | 24 | PK | | | 9-0 | 21-61-61 | D13402 | | | | X2 | | | TB0272Y | A031 | BJ | | 050-099 |
| 16N | 24 | PK | | | 8-0 | 21-61-61 | TB0272Y | | | | A031 | BJ | | D13402 | X2 | | | 150-199, 275-299 |
| 16P | 24 | PK | | | 8-0 | 21-61-61 | D13402 | | | | X1 | | | D05658J | 9 | | | 050-099 |
| 16P | 24 | PK | | | 7-0 | 21-61-61 | D05658J | | | | 9 | | | D13402 | X1 | | | 150-199, 275-299 |
| 16R | 24 | PK | | | 8-0 | 21-61-61 | TB0250Y | | | | A011 | BJ | | D05497J | 21 | | | 050-099 |
| 16R | 24 | PK | | | 4-0 | 21-61-61 | TB0272Y | | | | A023 | BJ | | D05497J | 21 | | | 150-199, 275-278 |
| 16R | 24 | PK | | | 6-0 | 21-61-61 | TB0250Y | | | | A011 | BJ | | D05497J | 21 | | | 280-299 |
| 16S | 24 | PK | | | 8-0 | 21-61-61 | D13404 | | | | B1 | | | D05497J | 20 | | | 050-099 |
| 16S | 24 | PK | | | 5-0 | 21-61-61 | D13404 | | | | B1 | | | D05497J | 20 | | | 150-199, 275-299 |
| 16T | 24 | PK | | | 8-0 | 21-61-61 | D13404 | | | | B2 | | | D05497J | 22 | | | 050-099 |
| 16T | 24 | PK | | | 5-0 | 21-61-61 | D13404 | | | | B2 | | | D05497J | 22 | | | 150-199, 275-299 |
| 16UB | 24 | PL | EJ | | 8-0 | 21-61-61 | D13402 | | | | B3 | | | D05497J | 11 | | | 050-099 |
| 16UB | 24 | PL | BO | | 7-0 | 21-61-61 | D05497J | | | | 11 | | | D13402 | B3 | | | 150-199, 275-299 |
| 16UR | 24 | PL | EJ | | 0-0 | 21-61-61 | D13402 | | | | C3 | | | D05497J | 12 | | | 050-099 |
| 16UR | 24 | PL | BO | | 0-0 | 21-61-61 | D05497J | | | | 12 | | | D13402 | C3 | | | 150-199, 275-299 |
| 16V | 24 | PK | | | 8-0 | 21-61-61 | D13402 | | | | C2 | | | D04904J | 17 | | | 050-099 |
| 16V | 24 | PK | | | 7-0 | 21-61-61 | D13402 | | | | C2 | | | D04904J | 17 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 21

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 16W | 24 | | PK | 8-0 | 21-61-61 | D13402 | | C1 | | | | | D04904J | 18 | | | 050-099 |
| 16W | 24 | | PK | 7-0 | 21-61-61 | D13402 | | C1 | | | | | D04904J | 18 | | | 150-199, 275-299 |
| 16X | 24 | | PK | 8-0 | 21-61-61 | D13402 | | B2 | | | | | D04904J | 19 | | | 050-099 |
| 16X | 24 | | PK | 7-0 | 21-61-61 | D13402 | | B2 | | | | | D04904J | 19 | | | 150-199, 275-299 |
| 170 | 24 | | PK | 9-0 | 21-58-12 | TB0252Z | | 6 | | BJ | | | D03586 | X1 | | | ALL |
| 172 | 24 | | PK | 6-0 | 24-22-11 | D03514 | | 1 | | | | | TB0220Y | A020 | BJ | | ALL |
| 173 | 22 | | PA | 4-0 | 74-31-11 | D05308J | | 2 | | | | | TB0222X | C007 | BJ | | ALL |
| 174 | 24 | | PK | 6-0 | 36-23-21 | D00598 | | 1 | | | | | TB0218X | A002 | BJ | | ALL |
| 175 | 24 | | PK | 9-0 | 21-58-12 | D03586 | | X2 | | | | | TB0272Y | C023 | BJ | | ALL |
| 176 | 24 | | PK | 6-0 | 21-58-13 | D03586 | | A1 | | | | | D04904J | 21 | | | 050-099, 275-299 |
| 176 | 24 | | PK | 7-0 | 21-58-13 | D03586 | | A1 | | | | | D04904J | 21 | | | 150-199 |
| 17A | 24 | | PK | 5-0 | 21-61-61 | D13406 | | 7 | | | | | TB0272D | C033 | 2 | | 050-099 |
| 17A | 24 | | PK | 4-0 | 21-61-61 | D13406 | | 7 | | | | | TB0272D | C033 | 2 | | 150-199, 275-299 |
| 17B | 24 | | PK | 5-0 | 21-61-61 | D13406 | | 3 | | | | | TB0272D | A033 | 2 | | 050-099 |
| 17B | 24 | | PK | 4-0 | 21-61-61 | D13406 | | 3 | | | | | TB0272D | A033 | 2 | | 150-199, 275-299 |
| 17C | 24 | | PK | 5-0 | 21-61-61 | TB0250Y | | A011 | | BJ | | | TB0272D | A033 | 2 | | 050-099 |
| 17C | 24 | | PK | 2-0 | 21-61-61 | TB0272D | | A033 | 2 | | | | TB0272Y | A023 | BJ | | 150-199, 275-278 |
| 17C | 24 | | PK | 6-0 | 21-61-61 | TB0272D | | A033 | 2 | | | | TB0250Y | A011 | BJ | | 280-299 |
| 17D | 24 | | PK | 4-0 | 21-61-61 | D13406 | | 5 | | | | | TB0250Y | A011 | BJ | | 050-099, 280-299 |
| 17D | 24 | | PK | 5-0 | 21-61-61 | D13406 | | 5 | | | | | TB0272Y | A023 | BJ | | 150-199, 275-278 |
| 17E | 24 | | PK | 5-0 | 21-61-61 | D13406 | | 1 | | | | | TB0272Y | A031 | BJ | | ALL |
| 17F | 20 | | PA | 4-0 | 21-61-61 | D13406 | | 6 | | | | | GDX0009 | D.. | 2 | | 050-099 |
| 17F | 20 | | PA | 5-0 | 21-61-61 | D13406 | | 6 | | | | | GDX0009 | D.. | 2 | | 150-199 |
| 17F | 20 | | PA | 6-0 | 21-61-61 | D13406 | | 6 | | | | | GDX0009 | D.. | 2 | | 275-299 |
| 17G | 24 | | PK | 7-0 | 21-61-61 | D13404 | | X2 | | | | | D05658J | 36 | | | 050-099 |
| 17G | 24 | | PK | 5-0 | 21-61-61 | D13404 | | X2 | | | | | D05658J | 36 | | | 150-199, 275-299 |
| 17H | 24 | | PK | 5-0 | 21-61-61 | TB0272Y | | A031 | | BJ | | | D05658J | 32 | | | 050-099 |
| 17H | 24 | | PK | 4-0 | 21-61-61 | TB0272Y | | A031 | | BJ | | | D05658J | 32 | | | 150-199, 275-299 |
| 17J | 24 | | PK | 8-0 | 31-31-26 | D05497J | | 14 | | | | | TB0078Y | A001 | BJ | | 050-099 |
| 17J | 24 | | PK | 7-0 | 31-31-26 | TB0078Y | | A001 | | BJ | | | D05497J | 14 | | | 150-199, 275-299 |
| 17K | 24 | | PK | 8-0 | 31-31-26 | D05497J | | 15 | | | | | TB0078Y | C001 | BJ | | 050-099 |
| 17K | 24 | | PK | 7-0 | 31-31-26 | TB0078Y | | C001 | | BJ | | | D05497J | 15 | | | 150-199, 275-299 |
| 17M | 20 | | PA | 4-0 | 21-28-11 | D13396 | | 4 | | | | | GDX0001 | D.. | 2 | | ALL |
| 17N | 22 | | PA | 8-0 | 21-28-11 | D13432 | | A3 | | | | | D05658J | 44 | | | 050-099 |
| 17N | 22 | | PA | 7-0 | 21-28-11 | D13432 | | A3 | | | | | D05658J | 44 | | | 150-199, 275-276 |
| 17N | 22 | | PA | 7-0 | 21-28-11 | D13432 | | A3 | | | | | D04904J | 24 | | | 277-299 |
| 17R | 22 | | PA | 8-0 | 21-28-11 | D13432 | | A1 | | | | | D05658J | 45 | | | 050-099 |
| 17R | 22 | | PA | 7-0 | 21-28-11 | D13432 | | A1 | | | | | D05658J | 45 | | | 150-199, 275-276 |
| 17R | 22 | | PA | 7-0 | 21-28-11 | D13432 | | A1 | | | | | D04904J | 23 | | | 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 22

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 17S | 24 | | PK | | 3-0 | 21-28-11 | D13396 | | | 5 | | | D13432 | X2 | | 050-099 |
| 17S | 24 | | PK | | 2-0 | 21-28-11 | D13396 | | | 5 | | | D13432 | X2 | | 150-199, 275-299 |
| 17T | 24 | | PK | | 8-0 | 21-28-11 | D13432 | | | X1 | | | D05658J | 46 | | 050-099 |
| 17T | 24 | | PK | | 7-0 | 21-28-11 | D05658J | | | 46 | | | D13432 | X1 | | 150-199, 275-299 |
| 17U | 22 | | PA | | 5-0 | 78-36-11 | D05300J | | | 42 | | | TB0272Y | C006 | BJ | 150-199 |
| 180 | 20 | | PA | | 3-0 | 36-23-21 | D00598 | | | 2 | | | GDY0007 | D.. | 2 | ALL |
| 183 | 24 | | PK | | 8-0 | 21-61-71 | D13408 | | | X1 | | | D04662J | 17 | | 050-099 |
| 183 | 24 | | PK | | 7-0 | 21-61-71 | D04662J | | | 17 | | | D13408 | X1 | | 150-199, 275-299 |
| 187 | 24 | | PK | | 6-0 | 21-58-13 | D04904J | | | 22 | | | D03586 | A3 | | 050-099, 275-299 |
| 187 | 24 | | PK | | 7-0 | 21-58-13 | D04904J | | | 22 | | | D03586 | A3 | | 150-199 |
| 18D | 20 | | PA | | 7-0 | 24-51-72 | K02091 | | | X1 | C | | TB0074D | C015 | 2 | 050-099, 162-164, 276 |
| 18E | 20 | | PA | | 5-0 | 24-51-72 | D05658J | | | 42 | | | K02091 | X2 | C | 050-099 |
| 18E | 20 | | PA | | 7-0 | 24-51-72 | GDY0004 | | | D.. | 2 | | K02091 | X2 | C | 155-157, 165-199, 277-299 |
| 18E | 20 | | PA | | 6-0 | 24-51-72 | D05658J | | | 42 | | | K02091 | X2 | C | 162-164, 276 |
| 18H | 22 | | PQ | ES | 3-0 | 73-21-11 | D12246 | | | 5 | | | D12250 | X2 | | 050-099 |
| 18H | 22 | | PQ | EF | 3-0 | 73-21-11 | D12250 | | | X2 | | | D12246 | 5 | | 150-199, 275-276 |
| 18H | 22 | | PQ | EF | 2-0 | 73-21-11 | D12250 | | | X2 | | | D12246 | 5 | | 277-299 |
| 18HZ | | | | ES | 0-0 | 73-21-11 | D12246 | | | DED | | | D12250 | DED | | 050-099 |
| 18HZ | | | | EF | 0-0 | 73-21-11 | D12250 | | | DED | | | D12246 | DED | | 150-199, 275-299 |
| 18K | 22 | | PQ | ET | 8-0 | 73-21-11 | D12250 | | | X1 | | | TB0318H | 33 | 2 | 050-099 |
| 18K | 22 | | PQ | EH | 6-0 | 73-21-11 | D12250 | | | X1 | | | TB0318H | 33 | 2 | 150-199 |
| 18K | 22 | | PQ | EH | 8-0 | 73-21-11 | D12250 | | | X1 | | | TB0318H | 33 | 2 | 275-276 |
| 18K | 22 | | PQ | EH | 7-0 | 73-21-11 | D12250 | | | X1 | | | TB0318H | 33 | 2 | 277-299 |
| 18KZ | | | | ET | 0-0 | 73-21-11 | D12250 | | | DED | | | TB0318H | DED | | 050-099 |
| 18KZ | | | | EH | 0-0 | 73-21-11 | D12250 | | | DED | | | TB0318H | DED | | 150-199, 275-299 |
| 18L | 20 | | PA | | 8-0 | 73-21-11 | D12250 | | | A1 | | | TB0302Y | A025 | BJ | 050-099 |
| 18L | 20 | | PA | | 6-0 | 73-21-11 | D12250 | | | A1 | | | TB0318Y | A016 | BJ | 150-199 |
| 18L | 20 | | PA | | 8-0 | 73-21-11 | D12250 | | | A1 | | | TB0318Y | A016 | BJ | 275-276 |
| 18L | 20 | | PA | | 7-0 | 73-21-11 | D12250 | | | A1 | | | TB0302Y | A025 | BJ | 277-299 |
| 18M | 22 | | PQ | EU | 8-0 | 73-21-11 | D12250 | | | Y1 | | | TB0318H | 33 | 2 | 050-099 |
| 18M | 22 | | PQ | EI | 6-0 | 73-21-11 | D12250 | | | Y1 | | | TB0318H | 33 | 2 | 150-199 |
| 18M | 22 | | PQ | EI | 8-0 | 73-21-11 | D12250 | | | Y1 | | | TB0318H | 33 | 2 | 275-276 |
| 18M | 22 | | PQ | EI | 7-0 | 73-21-11 | D12250 | | | Y1 | | | TB0318H | 33 | 2 | 277-299 |
| 18MZ | | | | EU | 0-0 | 73-21-11 | D12250 | | | DED | | | TB0318H | DED | | 050-099 |
| 18MZ | | | | EI | 0-0 | 73-21-11 | D12250 | | | DED | | | TB0318H | DED | | 150-199, 275-299 |
| 18N | 20 | | PA | | 4-0 | 73-21-11 | D12250 | | | A2 | | | GDY0003 | D.. | 2 | 050-099, 275-276 |
| 18N | 20 | | PA | | 5-0 | 73-21-11 | D12250 | | | A2 | | | GDY0003 | D.. | 2 | 150-199, 277-299 |
| 18P | 22 | | PQ | EV | 5-0 | 73-21-11 | D12250 | | | Y2 | | | D11750 | B1 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 23

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 18P | 22 | PQ | EJ | 5-0 | 73-21-11 | D12250 | | Y2 | | | | D11750 | B1 | | 150-199, 275-299 | |
| 18PZ | | | EV | 0-0 | 73-21-11 | D12250 | | DED | | | | D11750 | DED | | 050-099 | |
| 18PZ | | | EJ | 0-0 | 73-21-11 | D12250 | | DED | | | | D11750 | DED | | 150-199, 275-299 | |
| 18R | 20 | PA | | 5-0 | 73-21-11 | D05308J | | 12 | | | | TB0302Y | A025 | BJ | 050-099, 277-299 | |
| 18R | 20 | PA | | 5-0 | 73-21-11 | D05308J | | 12 | | | | TB0318Y | A016 | BJ | 150-199, 275-276 | |
| 18S | 20 | PA | | 8-0 | 73-21-11 | D11798 | | 2 | | | | TB0302Y | A025 | BJ | 050-099, 277-299 | |
| 18S | 20 | PA | | 8-0 | 73-21-11 | D11798 | | 2 | | | | TB0318Y | A016 | BJ | 150-199, 275-276 | |
| 18T | 20 | PA | | 7-0 | 73-21-11 | D11798 | | 13 | | | | D11750 | B2 | | 050-099 | |
| 18T | 20 | PA | | 7-0 | 73-21-11 | D11750 | | B2 | | | | D11798 | 13 | | 150-199, 275-299 | |
| 18U | 20 | PA | | 8-0 | 73-21-11 | D13628 | | X2 | | | | TB0302Y | A025 | BJ | 050-099, 277-299 | |
| 18U | 20 | PA | | 8-0 | 73-21-11 | D13628 | | X2 | | | | TB0318Y | A016 | BJ | 150-199, 275-276 | |
| 18V | 20 | PA | | 8-0 | 73-21-11 | D13628 | | X1 | | | | TB0318H | 33 | 2 | ALL | |
| 18X | 16 | PQ | EF | 8-0 | 73-21-11 | D13628 | | A1 | | | | D05832J | 55 | FL | 050-099 | |
| 18X | 16 | PQ | EK | 8-0 | 73-21-11 | D13628 | | A1 | | | | D05832J | 55 | FM | 150-154 | |
| 18X | 16 | PQ | EK | 8-0 | 73-21-11 | D13628 | | A1 | | | | D05832J | 55 | FL | 155-199, 275-299 | |
| 18XZ | | | EF | 0-0 | 73-21-11 | D13628 | | | | GF | | D05832J | 54 | | 050-099 | |
| 18XZ | | | EK | 0-0 | 73-21-11 | D13628 | | | | FM | | D05832J | 54 | | 150-199, 275-299 | |
| 18Y | 16 | PA | | 8-0 | 73-21-11 | D13628 | | A2 | | | | TB0318H | 33 | 2 | ALL | |
| 190 | 24 | PK | | 6-0 | 36-11-11 | D05658J | | 16 | | | | TB0074Y | A011 | BJ | ALL | |
| 191 | 22 | PA | | 6-0 | 36-11-11 | D05658J | | 19 | | | | D03476 | A2 | | ALL | |
| 192 | 22 | PA | | 6-0 | 36-11-11 | D05658J | | 20 | | | | D03474 | A2 | | ALL | |
| 193 | 24 | PK | | 3-0 | 36-11-11 | TB0074Y | | A011 | BJ | | | D03476 | X1 | | ALL | |
| 194 | 24 | PK | | 3-0 | 36-11-11 | TB0074Y | | A011 | BJ | | | D03474 | X1 | | ALL | |
| 195 | 24 | PK | | 4-0 | 36-11-11 | D04904J | | 29 | | | | D05658J | 17 | | ALL | |
| 196 | 24 | PK | | 4-0 | 36-11-11 | D04904J | | 33 | | | | D05658J | 18 | | ALL | |
| 197 | 20 | PA | | 3-0 | 36-11-11 | GDX0005 | | D.. | 2 | | | D03476 | A3 | | ALL | |
| 198 | 24 | PK | | 6-0 | 36-11-11 | D04904J | | 53 | | | | D03476 | X2 | | ALL | |
| 199 | 20 | PA | | 3-0 | 36-11-11 | GDX0005 | | D.. | 2 | | | D03474 | A3 | | ALL | |
| 199A | 20 | PA | | 4-0 | 34-22-36 | D03610 | | 1 | | | | GDX0006 | S.. | 2 | 050-099 | |
| 199A | 20 | PA | | 3-0 | 34-22-36 | D03610 | | 1 | | | | GDX0006 | S.. | 2 | 150-199, 275-299 | |
| 199B | 20 | PA | | 7-0 | 34-22-36 | D05431J | | 18 | | | | D03610 | 2 | | 050-099 | |
| 199B | 20 | PA | | 6-0 | 34-22-36 | D03610 | | 2 | | | | D05431J | 18 | | 150-199, 275-299 | |
| 19A | 24 | PK | | 5-0 | 21-58-16 | D04662J | | 22 | | | | TB0252D | A005 | 2 | 150-199, 275-299 | |
| 19B | 24 | PK | | 5-0 | 21-58-16 | D04662J | | 24 | | | | TB0252D | A008 | 2 | 150-199, 275-299 | |
| 19C | 24 | PK | | 2-0 | 21-58-16 | TB0252D | | C005 | 2 | | | TB0252D | C008 | 2 | 150-199, 275-299 | |
| 19E | 24 | PK | | 3-0 | 21-58-16 | TB0252D | | C008 | 2 | | | D10890 | B1 | | 150-199 | |
| 19E | 24 | PK | | 4-0 | 21-58-16 | TB0252D | | C008 | 2 | | | D10890 | B1 | | 275-299 | |
| 19F | 20 | PA | | 5-0 | 21-58-16 | D10890 | | B2 | | | | GDX0015 | D.. | 2 | 150-199, 275-299 | |
| 19G | 24 | PK | | 8-0 | 73-21-18 | D05300J | | 60 | | | | D13578 | 12 | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 24

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 19G | 24 | | PK | | 7-0 | 73-21-18 | D05300J | 60 | | | D13578 | 12 | | | 150-199, 275-299 |
| 19H | 24 | | PK | | 9-0 | 73-21-18 | TB0220Y | A001 | BJ | | D13578 | 6 | | | 050-099 |
| 19H | 24 | | PK | | 7-0 | 73-21-18 | D13578 | 6 | | | TB0220Y | A001 | BJ | | 150-154, 277-299 |
| 19H | 24 | | PK | | 9-0 | 73-21-18 | D13578 | 6 | | | TB0220Y | A001 | BJ | | 155-199 |
| 19H | 24 | | PK | | 9-0 | 73-21-18 | D13578 | 6 | | | TB0220Y | A001 | 9J | | 275-276 |
| 19J | 22 | | PA | | 9-0 | 32-45-11 | D13578 | 13 | | | TB0272X | C014 | BJ | | 050-099 |
| 19J | 22 | | PA | | 10-0 | 32-45-11 | TB0272Y | C026 | BJ | | D13578 | 13 | | | 150 |
| 19J | 22 | | PA | | 12-0 | 32-45-11 | TB0272X | C014 | BJ | | D13578 | 13 | | | 151-199 |
| 19J | 22 | | PA | | 10-0 | 32-45-11 | D06286J | 5 | | | D13578 | 13 | | | 275-299 |
| 19K | 22 | | PA | | 4-0 | 32-45-11 | D13578 | 1 | | | GD0001 | D.. | 2 | | 050-099 |
| 19K | 22 | | PA | | 7-0 | 32-45-11 | D13578 | 1 | | | GD0001 | D.. | 2 | | 150-199, 275-299 |
| 19L | 24 | | PK | | 10-0 | 32-09-11 | D13396 | 12 | | | TB0074Z | 5 | BJ | | 050-099 |
| 19L | 24 | | PK | | 10-0 | 32-09-11 | TB0074Z | 5 | BJ | | D13396 | 12 | | | 150-199 |
| 19L | 24 | | PK | | 13-0 | 32-09-11 | D13396 | 12 | | | TB0074Z | 5 | BJ | | 275-299 |
| 19M | 24 | | PK | | 10-0 | 32-09-11 | D13396 | 6 | | | TB0076Y | A004 | BJ | | 050-099 |
| 19M | 24 | | PK | | 10-0 | 32-09-11 | TB0076Y | A004 | BJ | | D13396 | 6 | | | 150-199 |
| 19M | 24 | | PK | | 9-0 | 32-09-11 | TB0076Z | 7 | BJ | | D13396 | 6 | | | 275-276 |
| 19M | 24 | | PK | | 9-0 | 32-09-11 | TB0076Y | A004 | BJ | | D13396 | 6 | | | 277-299 |
| 19N | 24 | | PK | | 2-0 | 32-09-11 | TB0076Z | 7 | BJ | | TB0076Y | A004 | BJ | | ALL |
| 19P | 20 | | UA | | 9-0 | 73-21-11 | D13628 | | | GF | GD0003 | S.. | 2 | | 050-099 |
| 19P | 20 | | UA | | 11-0 | 73-21-11 | D13628 | | | FM | GD0003 | S.. | 2 | | 150-199, 277-299 |
| 19P | 20 | | UA | | 9-0 | 73-21-11 | D13628 | | | FM | GD0003 | S.. | 2 | | 275-276 |
| 19R | 16 | | PA | | 5-0 | 73-21-11 | D05308J | 16 | FL | | TB0318H | 33 | 2 | | 050-099, 275-276, 280-299 |
| 19R | 16 | | PA | | 5-0 | 73-21-11 | D05308J | 16 | FM | | TB0318H | 33 | 2 | | 150-199, 277-278 |
| 19S | 20 | | PA | | 8-0 | 73-21-11 | D11798 | 1 | | | GD0005 | D.. | 2 | | ALL |
| 19T | 20 | | PA | | 5-0 | 73-21-11 | D12246 | 2 | | | GD0003 | D.. | 2 | | ALL |
| 19UB | 24 | | PW | EQ | 4-0 | 31-35-14 | D05433J | 5 | | | D06582J | 26 | | | 050-099 |
| 19UB | 24 | | PW | EE | 4-0 | 31-35-14 | D05433J | 5 | | | D06582J | 26 | | | 150-199, 275-276, 278-299 |
| 19UR | 24 | | PW | EQ | 0-0 | 31-35-14 | D05433J | 4 | | | D06582J | 25 | | | 050-099 |
| 19UR | 24 | | PW | EE | 0-0 | 31-35-14 | D05433J | 4 | | | D06582J | 25 | | | 150-199, 275-276, 278-299 |
| 19UZ | | | | EQ | 0-0 | 31-35-14 | D05433J | 6 | | | D06582J | 27 | | | 050-099 |
| 19UZ | | | | EE | 0-0 | 31-35-14 | D05433J | 6 | | | D06582J | 27 | | | 150-199, 275-276, 278-299 |
| 19Y | 20 | | PQ | GW | 5-0 | 78-34-11 | D05308J | 8 | | | D04709J | 25 | | | ALL |
| 19YZ | | | | GW | 0-0 | 78-34-11 | D05308J | | | HM | D04709J | | | GU | ALL |
| 200B | 24 | | PL | EK | 6-0 | 21-61-71 | D13408 | B3 | | | D05431J | 21 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 25

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 200B | 24 | PL | BI | 7-0 | 21-61-71 | D05431J | | 21 | | | | D13408 | B3 | | 150-199, 275-299 | |
| 200R | 24 | PL | EK | 0-0 | 21-61-71 | D13408 | | C3 | | | | D05431J | 20 | | 050-099 | |
| 200R | 24 | PL | BI | 0-0 | 21-61-71 | D05431J | | 20 | | | | D13408 | C3 | | 150-199, 275-299 | |
| 202B | 24 | PL | F | 6-0 | 21-31-11 | D10342 | | 5 | | | | D05060J | 5 | | ALL | |
| 202R | 24 | PL | F | 0-0 | 21-31-11 | D10342 | | 4 | | | | D05060J | 6 | | ALL | |
| 203B | 24 | PL | E | 5-0 | 21-51-12 | D03610 | | 5 | | | | D04904J | 13 | | ALL | |
| 203R | 24 | PL | E | 0-0 | 21-51-12 | D03610 | | 3 | | | | D04904J | 14 | | ALL | |
| 205B | 22 | PB | L | 3-0 | 32-61-13 | D04672J | | 3 | | | | D05576J | 6 | | ALL | |
| 205R | 22 | PB | L | 0-0 | 32-61-13 | D04672J | | 2 | | | | D05576J | 5 | | ALL | |
| 206B | 22 | PB | M | 3-0 | 32-61-13 | D04672J | | 5 | | | | D05576J | 8 | | ALL | |
| 206R | 22 | PB | M | 0-0 | 32-61-13 | D04672J | | 4 | | | | D05576J | 7 | | ALL | |
| 207B | 22 | PB | N | 3-0 | 32-61-13 | D04672J | | 7 | | | | D05576J | 10 | | ALL | |
| 207R | 22 | PB | N | 0-0 | 32-61-13 | D04672J | | 6 | | | | D05576J | 9 | | ALL | |
| 208B | 22 | PB | P | 3-0 | 32-61-13 | D04672J | | 13 | | | | D05576J | 12 | | ALL | |
| 208R | 22 | PB | P | 0-0 | 32-61-13 | D04672J | | 12 | | | | D05576J | 11 | | ALL | |
| 209B | 24 | PL | R | 5-0 | 36-21-11 | D05658J | | 39 | | | | TB0302Y | A029 | BJ | 050-099, 150-199 | |
| 209B | 24 | PL | R | 4-0 | 36-21-11 | D05658J | | 39 | | | | TB0302Y | A029 | BJ | 275-299 | |
| 209R | 24 | PL | R | 0-0 | 36-21-11 | D05658J | | 38 | | | | TB0302Y | C029 | BJ | ALL | |
| 20A | 24 | PK | | 5-0 | 21-43-11 | D05658J | | 49 | | | | TB0302X | C001 | BJ | ALL | |
| 20B | 24 | PK | | 5-0 | 21-43-11 | D05658J | | 48 | | | | TB0302X | B003 | BJ | ALL | |
| 20C | 24 | PK | | 5-0 | 21-43-11 | D04802J | | 4 | | | | TB0302X | C003 | BJ | 050-099 | |
| 20C | 24 | PK | | 4-0 | 21-43-11 | D04802J | | 4 | | | | TB0302X | C003 | BJ | 150-199, 275-299 | |
| 20D | 24 | PK | | 5-0 | 21-58-16 | D04672J | | 34 | | | | TB0272Z | 16 | BJ | 050-099 | |
| 20D | 24 | PK | | 5-0 | 21-58-16 | TB0272Z | | 16 | BJ | | | D04672J | 34 | | 150-199, 275-299 | |
| 20RB | 24 | PW | FL | 5-0 | 34-45-14 | D05431J | | 13 | | | | TB0222Y | A020 | BJ | 050-099, 150-152, 155-199 | |
| 20RB | 24 | PW | FL | 8-0 | 34-45-14 | D05431J | | 13 | | | | TB0222Y | A020 | BJ | 153-154 | |
| 20RB | 24 | PW | FL | 5-0 | 34-45-14 | D05431J | | 13 | | | | TB0222Y | A015 | BJ | 275-299 | |
| 20RR | 24 | PW | FL | 0-0 | 34-45-14 | D05431J | | 14 | | | | TB0222Y | C020 | BJ | 050-099, 150-199 | |
| 20RR | 24 | PW | FL | 0-0 | 34-45-14 | D05431J | | 14 | | | | TB0222Y | C016 | BJ | 275-299 | |
| 20RZ | | | FL | 0-0 | 34-45-14 | D05431J | | 15 | | | | TB0222Y | C019 | BJ | 050-099, 150-199 | |
| 20RZ | | | FL | 0-0 | 34-45-14 | D05431J | | 15 | | | | TB0222Y | C015 | BJ | 275-299 | |
| 20T | 22 | PA | | 6-0 | 30-21-11 | D05930J | | 2 | | | | D12130 | 6 | | 050-099, 155-199 | |
| 20T | 22 | PA | | 7-0 | 30-21-11 | D05930J | | 2 | | | | D12130 | 6 | | 150-154 | |
| 20U | 22 | PA | | 4-0 | 30-21-11 | D12122 | | 13 | | | | TB0078Y | A008 | BJ | 050-099, 155-199 | |
| 20U | 22 | PA | | 5-0 | 30-21-11 | D12122 | | 13 | | | | TB0078Y | A008 | BJ | 150-154 | |
| 20Y | 22 | PA | | 9-0 | 30-21-11 | D05306J | | 28 | | | | TB0078Y | A008 | BJ | 050-099 | |
| 20Y | 22 | PA | | 8-0 | 30-21-11 | D05306J | | 28 | | | | TB0078Y | A008 | BJ | 150-154 | |
| 20Y | 22 | PA | | 7-0 | 30-21-11 | D05306J | | 28 | | | | TB0078Y | A008 | BJ | 155-199 | |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 26

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 212B | 22 | PB | AB | | 5-0 | 27-51-41 | D05300J | | 24 | | TB0302X | B005 | BJ | | ALL |
| 212R | 22 | PB | AB | | 0-0 | 27-51-41 | D05300J | | 25 | | TB0302X | A005 | BJ | | ALL |
| 213B | 24 | PL | AA | | 3-0 | 27-28-13 | D05300J | | 10 | | D05310J | 12 | | | ALL |
| 213R | 24 | PL | AA | | 0-0 | 27-28-13 | D05300J | | 9 | | D05310J | 11 | | | ALL |
| 215B | 24 | PL | AK | | 7-0 | 21-51-11 | D10142 | | 4 | | D04672J | 44 | | | ALL |
| 215R | 24 | PL | AK | | 0-0 | 21-51-11 | D10142 | | 2 | | D04672J | 45 | | | ALL |
| 216B | 24 | PW | AJ | | 5-0 | 73-21-14 | TB0302Z | | 21 | BJ | D05431J | 2 | | | ALL |
| 216R | 24 | PW | AJ | | 0-0 | 73-21-14 | TB0302Z | | 22 | BJ | D05431J | 1 | | | ALL |
| 216Z | | | AJ | | 0-0 | 73-21-14 | TB0302Y | | A017 | BJ | D05431J | 3 | | | ALL |
| 217B | 24 | PL | I | | 5-0 | 21-61-51 | D03612 | | 7 | | TB0218X | C001 | BJ | | ALL |
| 217R | 24 | PL | I | | 0-0 | 21-61-51 | D03612 | | 14 | | TB0218X | D001 | BJ | | ALL |
| 218B | 20 | PB | IR | | 3-0 | 36-22-21 | D05360J | | 49 | | D04932J | 42 | | | 050-099 |
| 218B | 20 | PB | CM | | 3-0 | 36-22-21 | D04932J | | 42 | | D05360J | 49 | | | 150-199, 275-299 |
| 218R | 20 | PB | IR | | 0-0 | 36-22-21 | D05360J | | 50 | | D04932J | 41 | | | 050-099 |
| 218R | 20 | PB | CM | | 0-0 | 36-22-21 | D04932J | | 41 | | D05360J | 50 | | | 150-199, 275-299 |
| 219B | 24 | PL | AD | | 3-0 | 29-31-11 | D05360J | | 10 | | D04932J | 26 | | | ALL |
| 219R | 24 | PL | AD | | 0-0 | 29-31-11 | D05360J | | 12 | | D04932J | 25 | | | ALL |
| 21A | 22 | PA | | | 5-0 | 21-66-11 | D06934J | | 1 | | TB0318X | A035 | BJ | | 050-099, 162-199 |
| 21B | 22 | PA | | | 5-0 | 21-66-11 | D13844 | | B3 | | TB0318D | A003 | 2 | | 050-099 |
| 21B | 22 | PA | | | 7-0 | 21-66-11 | D13844 | | B3 | | TB0318D | A003 | 2 | | 162-199 |
| 21D | 24 | VA | | | 6-0 | 21-45-24 | D06934J | | 37 | | TB0216Y | C012 | BJ | | 150-157, 275-277 |
| 21D | 24 | PK | | | 5-0 | 21-45-24 | D06934J | | 37 | | TB0216Y | C012 | BJ | | 278-299 |
| 21G | 24 | VA | | | 6-0 | 21-45-24 | D06934J | | 38 | | TB0074Y | C014 | BJ | | 150-157, 275-277 |
| 21G | 24 | PK | | | 6-0 | 21-45-24 | D06934J | | 38 | | TB0074Y | C014 | BJ | | 278-299 |
| 21H | 24 | PK | | | 9-0 | 30-81-11 | TB0078Y | | A008 | BJ | D05832J | 51 | | | 050-099 |
| 21H | 24 | PK | | | 8-0 | 30-81-11 | TB0078Y | | A008 | BJ | D05832J | 51 | | | 150-154 |
| 21H | 24 | PK | | | 7-0 | 30-81-11 | TB0078Y | | A008 | BJ | D05832J | 51 | | | 155-199 |
| 21J | 24 | VA | | | 8-0 | 21-45-21 | D03512 | | D2 | | TB0074Y | C014 | BJ | | 150-199 |
| 21J | 24 | PK | | | 13-0 | 21-45-21 | D03512 | | D2 | | TB0074Y | C014 | BJ | | 275-277 |
| 21J | 24 | PK | | | 8-0 | 21-45-21 | D03512 | | D2 | | TB0074Y | C014 | BJ | | 278-299 |
| 220B | 24 | PW | IT | | 4-0 | 27-32-11 | TB0222Y | | A020 | BJ | D05433J | 47 | | | 050-099, 275-299 |
| 220B | 24 | PW | IT | | 5-0 | 27-32-11 | TB0222Y | | A020 | BJ | D05433J | 47 | | | 150-199 |
| 220R | 24 | PW | IT | | 0-0 | 27-32-11 | TB0222Y | | C020 | BJ | D05433J | 46 | | | ALL |
| 220Z | | | IT | | 0-0 | 27-32-11 | TB0222Y | | C019 | BJ | D05433J | 52 | | | ALL |
| 221B | 24 | PW | IU | | 4-0 | 32-42-11 | D04906J | | 30 | | TB0222Y | A020 | BJ | | 050-099 |
| 221B | 24 | PW | IU | | 4-0 | 32-42-11 | TB0222Y | | A020 | BJ | D04906J | 30 | | | 150-199, 275-299 |
| 221R | 24 | PW | IU | | 0-0 | 32-42-11 | D04906J | | 29 | | TB0222Y | C020 | BJ | | 050-099 |
| 221R | 24 | PW | IU | | 0-0 | 32-42-11 | TB0222Y | | C020 | BJ | D04906J | 29 | | | 150-199, 275-299 |
| 221Z | | | IU | | 0-0 | 32-42-11 | D04906J | | 31 | | TB0222Y | C019 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 27

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|-----------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 221Z | | | | IU | 0-0 | 32-42-11 | TB0222Y | C019 | BJ | | D04906J | 31 | | | 150-199, 275-299 |
| 223B | 24 | PL | AQ | | 3-0 | 32-09-11 | D05576J | 4 | | | D04672J | 11 | | | 050-099, 275-299 |
| 223B | 24 | PL | AQ | | 4-0 | 32-09-11 | D05576J | 4 | | | D04672J | 11 | | | 150-199 |
| 223R | 24 | PL | AQ | | 0-0 | 32-09-11 | D05576J | 3 | | | D04672J | 10 | | | ALL |
| 224B | 24 | PW | BB | | 4-0 | 32-42-11 | D01172 | B1 | | | TB0272X | C001 | BJ | | ALL |
| 224R | 24 | PW | BB | | 0-0 | 32-42-11 | D01172 | A1 | | | TB0272X | D001 | BJ | | ALL |
| 224Z | | | | BB | 0-0 | 32-42-11 | D01172 | | | FG | TB0272X | A002 | BJ | | ALL |
| 225B | 24 | PW | BA | | 6-0 | 32-42-11 | D01172 | B3 | | | D05433J | 24 | | | ALL |
| 225R | 24 | PW | BA | | 0-0 | 32-42-11 | D01172 | A3 | | | D05433J | 23 | | | ALL |
| 225Z | | | | BA | 0-0 | 32-42-11 | D01172 | | | FG | D05433J | 25 | | | ALL |
| 226B | 24 | PW | BC | | 3-0 | 32-42-11 | D01172 | B2 | | | TB0222Y | A020 | BJ | | 050-099 |
| 226B | 24 | PW | BC | | 4-0 | 32-42-11 | D01172 | B2 | | | TB0222Y | A020 | BJ | | 150-199, 275-299 |
| 226R | 24 | PW | BC | | 0-0 | 32-42-11 | D01172 | A2 | | | TB0222Y | C020 | BJ | | ALL |
| 226Z | | | | BC | 0-0 | 32-42-11 | D01172 | | | FG | TB0222Y | C019 | BJ | | ALL |
| 22A | 20 | PA | | | 5-0 | 21-66-11 | D06934J | 2 | | | TB0318X | A011 | BJ | | 050-099, 162-199 |
| 22B | 22 | PA | | | 5-0 | 21-66-11 | TB0318D | A003 | 2 | | D06934J | 18 | | | 050-099, 162-199 |
| 22C | 20 | PQ | HH | | 12-0 | 78-34-11 | D20102 | A1 | | | D05306J | 24 | | | ALL |
| 22CZ | | | | HH | 0-0 | 78-34-11 | D20102 | DED | | | D05306J | | | HH | ALL |
| 22D | 20 | PQ | HJ | | 12-0 | 78-34-11 | D20102 | C3 | | | D05306J | 23 | | | ALL |
| 22DZ | | | | HJ | 0-0 | 78-34-11 | D20102 | DED | | | D05306J | | | HH | ALL |
| 22E | 22 | PA | | | 5-0 | 21-66-21 | D05060J | 10 | | | TB0318D | A006 | 2 | | 050-099, 162-199 |
| 22P | 20 | PA | | | 4-0 | 78-34-11 | TB0076Z | | | HJ | GD00016 | S.. | 2 | | ALL |
| 22R | 20 | PQ | HM | | 12-0 | 78-34-21 | D20092 | A1 | | | TB0080X | A015 | BJ | | ALL |
| 22RZ | | | | HM | 0-0 | 78-34-21 | D20092 | DED | | | TB0080X | | | HK | ALL |
| 22T | 20 | PQ | HN | | 12-0 | 78-34-21 | D20092 | A2 | | | TB0080X | B015 | BJ | | ALL |
| 22TZ | | | | HN | 0-0 | 78-34-21 | D20092 | DED | | | TB0080X | | | HK | ALL |
| 22W | 20 | PQ | HP | | 8-0 | 78-34-11 | TB0318Z | 29 | BJ | | TB0220Y | A019 | BJ | | 050-099, 157, 167-199, 277-299 |
| 22W | 20 | PQ | HP | | 12-0 | 78-34-11 | TB0318Z | 29 | BJ | | TB0220Y | A019 | BJ | | 150-156, 162-166, 275-276 |
| 22WZ | | | | HP | 0-0 | 78-34-11 | TB0318Z | | | HF | TB0220Y | | | HL | ALL |
| 22X | 20 | PA | | | 5-0 | 78-34-21 | D10950 | D3 | | | GD00002 | D.. | 2 | | ALL |
| 22Y | 20 | PQ | HW | | 5-0 | 78-34-11 | D05308J | 35 | | | D04709J | 22 | | | ALL |
| 22YZ | | | | HW | 0-0 | 78-34-11 | D05308J | | | HM | D04709J | | | GU | ALL |
| 234B | 24 | PL | AG | | 6-0 | 21-51-11 | D12278 | 6 | | | D10142 | 5 | | | 050-099 |
| 234B | 24 | PL | AG | | 6-0 | 21-51-11 | D05780J | 30 | | | D10142 | 5 | | | 150-199, 275-299 |
| 234R | 24 | PL | AG | | 0-0 | 21-51-11 | D12278 | 2 | | | D10142 | 1 | | | 050-099 |
| 234R | 24 | PL | AG | | 0-0 | 21-51-11 | D05780J | 31 | | | D10142 | 1 | | | 150-199, 275-299 |
| 235B | 24 | PW | JJ | | 5-0 | 73-21-14 | D05300J | 36 | | | TB0302Y | A016 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 28

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 235B | 24 | PW | AN | | 5-0 | 73-21-14 | D05300J | | 36 | | TB0302Y | A016 | BJ | | 150-199, 275-299 |
| 235R | 24 | PW | JJ | | 0-0 | 73-21-14 | D05300J | | 37 | | TB0302Y | C016 | BJ | | 050-099 |
| 235R | 24 | PW | AN | | 0-0 | 73-21-14 | D05300J | | 37 | | TB0302Y | C016 | BJ | | 150-199, 275-299 |
| 235Z | | | JJ | | 0-0 | 73-21-14 | D05300J | | 39 | | TB0302Y | A018 | BJ | | 050-099 |
| 235Z | | | AN | | 0-0 | 73-21-14 | D05300J | | 39 | | TB0302Y | A018 | BJ | | 150-199, 275-299 |
| 237B | 24 | PW | JL | | 4-0 | 73-21-14 | D05433J | | 14 | | TB0302Y | A016 | BJ | | 050-099 |
| 237B | 24 | PW | AR | | 5-0 | 73-21-14 | D05433J | | 14 | | TB0302Y | A016 | BJ | | 150-199, 275-299 |
| 237R | 24 | PW | JL | | 0-0 | 73-21-14 | D05433J | | 13 | | TB0302Y | C016 | BJ | | 050-099 |
| 237R | 24 | PW | AR | | 0-0 | 73-21-14 | D05433J | | 13 | | TB0302Y | C016 | BJ | | 150-199, 275-299 |
| 237Z | | | JL | | 0-0 | 73-21-14 | D05433J | | 15 | | TB0302Y | A018 | BJ | | 050-099 |
| 237Z | | | AR | | 0-0 | 73-21-14 | D05433J | | 15 | | TB0302Y | A018 | BJ | | 150-199, 275-299 |
| 238B | 24 | PW | AS | | 5-0 | 73-21-14 | D05306J | | 49 | | TB0302Y | A016 | BJ | | ALL |
| 238R | 24 | PW | AS | | 0-0 | 73-21-14 | D05306J | | 50 | | TB0302Y | C016 | BJ | | ALL |
| 238Z | | | AS | | 0-0 | 73-21-14 | D05306J | | 46 | | TB0302Y | A018 | BJ | | ALL |
| 239B | 24 | PW | SC | | 4-0 | 73-21-17 | D04802J | | 27 | | D06582J | 19 | | | 050-099 |
| 239B | 24 | PW | SC | | 5-0 | 73-21-17 | D04802J | | 27 | | D06582J | 19 | | | 150-199 |
| 239B | 24 | PW | AT | | 5-0 | 73-21-17 | D04802J | | 27 | | D06582J | 19 | | | 275-299 |
| 239R | 24 | PW | SC | | 0-0 | 73-21-12 | D04802J | | 21 | | D06582J | 14 | | | 050-099, 150-199 |
| 239R | 24 | PW | AT | | 0-0 | 73-21-12 | D04802J | | 21 | | D06582J | 14 | | | 275-299 |
| 239Z | | | SC | | 0-0 | 73-21-12 | D04802J | | 28 | | D06582J | 15 | | | 050-099, 150-199 |
| 239Z | | | AT | | 0-0 | 73-21-12 | D04802J | | 28 | | D06582J | 15 | | | 275-299 |
| 23A | 20 | PA | | | 5-0 | 21-66-11 | D06934J | | 3 | | TB0318X | B011 | BJ | | 050-099, 162-199 |
| 23B | 22 | PA | | | 2-0 | 21-66-11 | TB0318D | C003 | 2 | | TB0318D | C002 | 2 | | 050-099, 162-199 |
| 23E | 22 | PA | | | 5-0 | 21-66-21 | D05060J | | 11 | | TB0318D | C006 | 2 | | 050-099, 162-199 |
| 241B | 24 | PW | BP | | 4-0 | 73-21-14 | D05308J | | 27 | | TB0302Z | 21 | BJ | | 050-099 |
| 241B | 24 | PW | AV | | 5-0 | 73-21-14 | D05308J | | 27 | | TB0302Z | 21 | BJ | | 150-199, 275-299 |
| 241R | 24 | PW | BP | | 0-0 | 73-21-14 | D05308J | | 28 | | TB0302Z | 22 | BJ | | 050-099 |
| 241R | 24 | PW | AV | | 0-0 | 73-21-14 | D05308J | | 28 | | TB0302Z | 22 | BJ | | 150-199, 275-299 |
| 241Z | | | BP | | 0-0 | 73-21-14 | D05308J | | 17 | | TB0302Y | A017 | BJ | | 050-099 |
| 241Z | | | AV | | 0-0 | 73-21-14 | D05308J | DED | | | TB0302Y | C025 | BJ | | 150-199 |
| 241Z | | | AV | | 0-0 | 73-21-14 | D05308J | | 17 | | TB0302Y | A017 | BJ | | 275-299 |
| 242B | 24 | PW | BO | | 4-0 | 73-21-14 | D05360J | | 28 | | TB0302Z | 21 | BJ | | 050-099 |
| 242B | 24 | PW | AW | | 5-0 | 73-21-14 | D05360J | | 28 | | TB0302Z | 21 | BJ | | 150-199, 275-299 |
| 242R | 24 | PW | BO | | 0-0 | 73-21-14 | D05360J | | 29 | | TB0302Z | 22 | BJ | | 050-099 |
| 242R | 24 | PW | AW | | 0-0 | 73-21-14 | D05360J | | 29 | | TB0302Z | 22 | BJ | | 150-199, 275-299 |
| 242Z | | | BO | | 0-0 | 73-21-14 | D05360J | | 53 | | TB0302Y | A017 | BJ | | 050-099 |
| 242Z | | | AW | | 0-0 | 73-21-14 | D05360J | | 53 | | TB0302Y | A017 | BJ | | 150-199, 275-299 |
| 245B | 24 | PL | CD | | 6-0 | 28-41-11 | D00340 | | C2 | | TB0272X | B003 | BJ | | ALL |
| 245R | 24 | PL | CD | | 0-0 | 28-41-11 | D00340 | | C1 | | TB0272Y | A005 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0170
Page 29
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | | |
| 246B | 24 | PL | CE | 5-0 | 28-41-11 | D10342 | | | | 9 | | | | TB0220X | A003 | BJ | | ALL |
| 246R | 24 | PL | CE | 0-0 | 28-41-11 | D10342 | | | | 11 | | | | TB0220X | B003 | BJ | | ALL |
| 248B | 20 | PB | CL | 2-0 | 21-44-22 | D05060J | | | | 8 | | | | D05360J | 26 | | | 050-099 |
| 248B | 20 | PB | EM | 4-0 | 21-44-22 | D05060J | | | | 8 | | | | D05360J | 26 | | | 150-199 |
| 248R | 20 | PB | CL | 0-0 | 21-44-22 | D05060J | | | | 9 | | | | D05360J | 27 | | | 050-099 |
| 248R | 20 | PB | EM | 0-0 | 21-44-22 | D05060J | | | | 9 | | | | D05360J | 27 | | | 150-199 |
| 249B | 24 | PW | CP | 5-0 | 77-31-11 | D05300J | | | | 54 | | | | TB0318Y | A019 | BJ | | 050-099, 277-299 |
| 249B | 24 | PW | DL | 5-0 | 77-31-11 | D05300J | | | | 54 | | | | TB0302Y | C026 | BJ | | 150-157 |
| 249B | 24 | PW | DL | 5-0 | 77-31-11 | D05300J | | | | 54 | | | | TB0318Y | A019 | BJ | | 162-199 |
| 249B | 24 | PW | CP | 5-0 | 77-31-11 | D05300J | | | | 54 | | | | TB0302Y | C026 | BJ | | 275-276 |
| 249R | 24 | PW | CP | 0-0 | 77-31-11 | D05300J | | | | 53 | | | | TB0318Y | A020 | BJ | | 050-099, 277-299 |
| 249R | 24 | PW | DL | 0-0 | 77-31-11 | D05300J | | | | 53 | | | | TB0302Y | A026 | BJ | | 150-157 |
| 249R | 24 | PW | DL | 0-0 | 77-31-11 | D05300J | | | | 53 | | | | TB0318Y | A020 | BJ | | 162-199 |
| 249R | 24 | PW | CP | 0-0 | 77-31-11 | D05300J | | | | 53 | | | | TB0302Y | A026 | BJ | | 275-276 |
| 249Z | | | CP | 0-0 | 77-31-11 | D05300J | | | | 55 | | | | TB0318Y | C019 | BJ | | 050-099, 277-299 |
| 249Z | | | DL | 0-0 | 77-31-11 | D05300J | | | | 55 | | | | TB0302Y | A027 | BJ | | 150-157 |
| 249Z | | | DL | 0-0 | 77-31-11 | D05300J | | | | 55 | | | | TB0318Y | C019 | BJ | | 162-199 |
| 249Z | | | CP | 0-0 | 77-31-11 | D05300J | | | | 58 | | | | TB0302Y | A027 | BJ | | 275-276 |
| 24A | 24 | PK | | 7-0 | 21-51-11 | D12278 | | | | 7 | | | | TB0076Z | 12 | BJ | | 050-099 |
| 24B | 24 | PK | | 7-0 | 21-61-51 | D04906J | | | | 24 | | | | TB0076Y | A005 | BJ | | 050-099 |
| 24N | 24 | PK | | 7-0 | 21-51-11 | R00660 | | | | = 1 | \$ | | | D12278 | 5 | | | 050-099 |
| 24P | 24 | PK | | 7-0 | 21-51-11 | R00660 | | | | = 2 | \$ | | | D12278 | 1 | | | 050-099 |
| 24R | 24 | PK | | 7-0 | 21-51-11 | D12278 | | | | 3 | | | | TB0076Y | A005 | BJ | | 050-099 |
| 24SB | 24 | PL | EN | 6-0 | 21-51-11 | D12278 | | | | 8 | | | | D05780J | 30 | | | 050-099 |
| 24SR | 24 | PL | EN | 0-0 | 21-51-11 | D12278 | | | | 4 | | | | D05780J | 31 | | | 050-099 |
| 250B | 24 | PW | DC | 5-0 | 34-61-15 | D01723 | | | | B1 | | | | D05497J | 8 | | | ALL |
| 250R | 24 | PW | DC | 0-0 | 34-61-15 | D01723 | | | | A1 | | | | D05497J | 9 | | | ALL |
| 250Z | | | DC | 0-0 | 34-61-15 | D01723 | | | | DED | | | | D05497J | 10 | | | ALL |
| 251B | 24 | PW | DD | 5-0 | 34-61-15 | D01723 | | | | B2 | | | | D05497J | 2 | | | ALL |
| 251R | 24 | PW | DD | 0-0 | 34-61-15 | D01723 | | | | A2 | | | | D05497J | 3 | | | ALL |
| 251Z | | | DD | 0-0 | 34-61-15 | D01723 | | | | DED | | | | D05497J | 4 | | | ALL |
| 252B | 24 | PW | DE | 5-0 | 34-61-15 | D01723 | | | | B3 | | | | D05497J | 5 | | | ALL |
| 252R | 24 | PW | DE | 0-0 | 34-61-15 | D01723 | | | | A3 | | | | D05497J | 6 | | | ALL |
| 252Z | | | DE | 0-0 | 34-61-15 | D01723 | | | | DED | | | | D05497J | 7 | | | ALL |
| 255B | 24 | PW | EC | 4-0 | 73-21-14 | D06582J | | | | 5 | | | | D05832J | 3 | | | 050-099 |
| 255B | 24 | PW | EC | 3-0 | 73-21-14 | D05832J | | | | 3 | | | | D06582J | 5 | C | | 150-199 |
| 255B | 24 | PW | EC | 5-0 | 73-21-14 | D05832J | | | | 3 | | | | D06582J | 5 | | | 275-299 |
| 255R | 24 | PW | EC | 0-0 | 73-21-14 | D06582J | | | | 6 | | | | D05832J | 4 | | | 050-099 |
| 255R | 24 | PW | EC | 0-0 | 73-21-14 | D05832J | | | | 4 | | | | D06582J | 6 | C | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 30

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|----------|---------|---------|-------|------|------|---------|-------|------|------|---|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 255R | 24 | PW | EC | 0-0 | 73-21-14 | D05832J | | 4 | | | D06582J | 6 | | | 275-299 |
| 255Z | | | EC | 0-0 | 73-21-14 | D06582J | | | | FJ | D05832J | 43 | | | 050-099 |
| 255Z | | | EC | 0-0 | 73-21-14 | D05832J | | 43 | | | D06582J | | | FS | 150-199, 275-299 |
| 256B | 24 | PW | DN | 5-0 | 73-21-14 | TB0302Z | | 21 | BJ | | D06582J | 3 | | | 050-099, 275-299 |
| 256B | 24 | PW | DN | 6-0 | 73-21-14 | D06582J | | 3 | | | TB0302Z | 21 | BJ | | 150-199 |
| 256R | 24 | PW | DN | 0-0 | 73-21-14 | TB0302Z | | 22 | BJ | | D06582J | 4 | | | ALL |
| 256Z | | | DN | 0-0 | 73-21-14 | TB0302Y | A017 | | BJ | | D06582J | | | FJ | 050-099 |
| 256Z | | | DN | 0-0 | 73-21-14 | D06582J | | | | FS | TB0302Y | A017 | BJ | | 150-199 |
| 256Z | | | DN | 0-0 | 73-21-14 | TB0302Y | A017 | | BJ | | D06582J | | | FS | 275-299 |
| 258B | 24 | PW | KH | 4-0 | 73-21-14 | D05433J | | 28 | | | D06582J | 10 | | | 050-099 |
| 258B | 24 | PW | CC | 4-0 | 73-21-14 | D05433J | | 28 | | | D06582J | 10 | | | 150-199, 275-299 |
| 258R | 24 | PW | KH | 0-0 | 73-21-14 | D05433J | | 27 | | | D06582J | 7 | | | 050-099 |
| 258R | 24 | PW | CC | 0-0 | 73-21-14 | D05433J | | 27 | | | D06582J | 7 | | | 150-199, 275-299 |
| 258Z | | | KH | 0-0 | 73-21-14 | D05433J | | 29 | | | D06582J | | | FH | 050-099 |
| 258Z | | | CC | 0-0 | 73-21-14 | D05433J | | 29 | | | D06582J | | | FC | 150-199, 275-299 |
| 259B | 24 | PL | HA | 5-0 | 36-21-11 | D04904J | | 7 | | | TB0302Y | A029 | BJ | | 050-099 |
| 259B | 24 | PL | DV | 5-0 | 36-21-11 | D04904J | | 7 | | | TB0302Y | A029 | BJ | | 150-155, 157, 163-165, 167-199 |
| 259B | 24 | PL | KI | 5-0 | 36-21-11 | D04904J | | 7 | | | TB0302Y | A029 | BJ | | 156, 162, 166 |
| 259B | 24 | PL | BF | 5-0 | 36-21-11 | D04904J | | 7 | | | TB0302Y | A029 | BJ | | 275-299 |
| 259R | 24 | PL | HA | 0-0 | 36-21-11 | D04904J | | 6 | | | TB0302Y | C029 | BJ | | 050-099 |
| 259R | 24 | PL | DV | 0-0 | 36-21-11 | D04904J | | 6 | | | TB0302Y | C029 | BJ | | 150-155, 157, 163-165, 167-199 |
| 259R | 24 | PL | KI | 0-0 | 36-21-11 | D04904J | | 6 | | | TB0302Y | C029 | BJ | | 156, 162, 166 |
| 259R | 24 | PL | BF | 0-0 | 36-21-11 | D04904J | | 6 | | | TB0302Y | C029 | BJ | | 275-299 |
| 25A | 20 | PA | | 5-0 | 21-66-11 | D06934J | | 4 | | | TB0318X | C011 | BJ | | 050-099, 162-199 |
| 25E | 22 | PA | | 2-0 | 21-66-21 | TB0318D | | | C006 | 2 | TB0318D | C007 | 2 | | 050-099, 162-199 |
| 260B | 24 | PL | HB | 5-0 | 36-21-11 | D04904J | | 61 | | | TB0302Y | A029 | BJ | | 050-099 |
| 260B | 24 | PL | DW | 5-0 | 36-21-11 | D04904J | | 61 | | | TB0302Y | A029 | BJ | | 150-155, 157, 163-165, 167-199, 275-299 |
| 260B | 24 | PL | KJ | 5-0 | 36-21-11 | D04904J | | 61 | | | TB0302Y | A029 | BJ | | 156, 162, 166 |
| 260R | 24 | PL | HB | 0-0 | 36-21-11 | D04904J | | 60 | | | TB0302Y | C029 | BJ | | 050-099 |
| 260R | 24 | PL | DW | 0-0 | 36-21-11 | D04904J | | 60 | | | TB0302Y | C029 | BJ | | 150-155, 157, 163-165, 167-199, 275-299 |
| 260R | 24 | PL | KJ | 0-0 | 36-21-11 | D04904J | | 60 | | | TB0302Y | C029 | BJ | | 156, 162, 166 |
| 26A | 22 | PA | | 5-0 | 21-66-11 | D06934J | | 5 | | | TB0318Z | 32 | BJ | | 050-099, 162-199 |
| 26E | 22 | PA | | 2-0 | 21-66-21 | TB0318D | | | C007 | 2 | TB0318D | C008 | 2 | | 050-099, 162-199 |

WIRE LIST
D280T132

91-21-11
Section W0170
Page 31
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|------|---------------------------------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0176 | 286T0176 | | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 270B | 24 | PW | DS | 5-0 | 77-12-12 | D04904J | | 9 | | | | TB0318Y | A019 | BJ | | 050-099, 162-199, 277-299 |
| 270B | 24 | PW | DS | 5-0 | 77-12-12 | D04904J | | 9 | | | | TB0302Y | C026 | BJ | | 150-157, 275-276 |
| 270R | 24 | PW | DS | 0-0 | 77-12-12 | D04904J | | 8 | | | | TB0318Y | A020 | BJ | | 050-099, 162-199, 277-299 |
| 270R | 24 | PW | DS | 0-0 | 77-12-12 | D04904J | | 8 | | | | TB0302Y | A026 | BJ | | 150-157, 275-276 |
| 270Z | | | DS | 0-0 | 77-12-12 | D04904J | | 10 | | | | TB0318Y | C019 | BJ | | 050-099, 277-299 |
| 270Z | | | DS | 0-0 | 77-12-12 | D04904J | | 10 | | | | TB0302Y | A027 | BJ | | 150-157, 275-276 |
| 270Z | | | DS | 0-0 | 77-12-12 | D04904J | | 10 | | | | TB0318Y | C019 | OJ | | 162-199 |
| 271B | 24 | PW | DT | 5-0 | 77-12-12 | D05360J | | 55 | | | | TB0318Y | A019 | BJ | | 050-099 |
| 271B | 24 | PW | DT | 5-0 | 77-12-12 | TB0302Y | | C026 | BJ | | | D05360J | | 55 | | 150-157, 275-276 |
| 271B | 24 | PW | DT | 5-0 | 77-12-12 | TB0318Y | | A019 | BJ | | | D05360J | | 55 | | 162-199, 277-299 |
| 271R | 24 | PW | DT | 0-0 | 77-12-12 | D05360J | | 54 | | | | TB0318Y | A020 | BJ | | 050-099 |
| 271R | 24 | PW | DT | 0-0 | 77-12-12 | TB0302Y | | A026 | BJ | | | D05360J | | 54 | | 150-157, 275-276 |
| 271R | 24 | PW | DT | 0-0 | 77-12-12 | TB0318Y | | A020 | BJ | | | D05360J | | 54 | | 162-199, 277-299 |
| 271Z | | | DT | 0-0 | 77-12-12 | D05360J | | 40 | | | | TB0318Y | C019 | BJ | | 050-099 |
| 271Z | | | DT | 0-0 | 77-12-12 | TB0302Y | | A027 | BJ | | | D05360J | | 40 | | 150-157, 275-276 |
| 271Z | | | DT | 0-0 | 77-12-12 | TB0318Y | | C019 | BJ | | | D05360J | | 40 | | 162-199, 277-299 |
| 272 | 22 | PA | | 5-0 | 30-21-11 | D11826 | | A2 | | | | TB0222Z | | 16 | BJ | 050-099 |
| 272 | 22 | PA | | 7-0 | 30-21-11 | TB0222Z | | 16 | BJ | | | D11826 | | A2 | | 150-154 |
| 272 | 22 | PA | | 6-0 | 30-21-11 | TB0222Z | | 16 | BJ | | | D11826 | | A2 | | 155-199 |
| 272 | 22 | PA | | 3-0 | 30-21-11 | D10160 | | C1 | | | | D11826 | | A2 | | 275-299 |
| 273 | 22 | PA | | 5-0 | 30-21-11 | D05306J | | 8 | | | | TB0250Y | C001 | BJ | | ALL |
| 274 | 22 | PA | | 9-0 | 30-21-11 | TB0080D | | C011 | 2 | | | D11826 | | X1 | | 050-099 |
| 274 | 22 | PA | | 10-0 | 30-21-11 | TB0080D | | C011 | 2 | | | D11826 | | X1 | | 150-199, 275-299 |
| 274B | 24 | PL | DI | 9-0 | 21-61-51 | D13396 | | 1 | | | | D04904J | | 3 | | 050-099 |
| 274B | 24 | PL | EQ | 8-0 | 21-61-51 | D04904J | | 3 | | | | D13396 | | 1 | | 150-199 |
| 274B | 24 | PL | EQ | 10-0 | 21-61-51 | D04904J | | 3 | | | | D13396 | | 1 | | 275-299 |
| 274R | 24 | PL | DI | 0-0 | 21-61-51 | D13396 | | 13 | | | | D04904J | | 5 | | 050-099 |
| 274R | 24 | PL | EQ | 0-0 | 21-61-51 | D04904J | | 5 | | | | D13396 | | 13 | | 150-199, 275-299 |
| 275 | 22 | PA | | 2-0 | 30-21-11 | D11826 | | X2 | | | | TB0250Y | C001 | BJ | | 050-099 |
| 275 | 22 | PA | | 3-0 | 30-21-11 | D11826 | | X2 | | | | TB0250Y | C001 | BJ | | 150-199, 275-299 |
| 276 | 22 | PA | | 2-0 | 30-21-11 | D11826 | | B1 | | | | TB0250Y | C001 | BJ | | 050-099 |
| 276 | 22 | PA | | 3-0 | 30-21-11 | D11826 | | B1 | | | | TB0250Y | C001 | BJ | | 150-199, 275-299 |
| 277 | 22 | PA | | 5-0 | 30-21-11 | TB0250Y | | C001 | BJ | | | D05360J | | 6 | | ALL |
| 278 | 20 | PA | | 2-0 | 30-21-11 | D11826 | | B2 | | | | GDX0017 | | D.. | 2 | ALL |
| 27A | 22 | PA | | 7-0 | 21-66-11 | TB0318Z | | 32 | BJ | | | D02912 | | 9 | | 050-099, 162-199 |
| 27A | 22 | PA | | 7-0 | 21-66-41 | TB0318Z | | 32 | BJ | | | D02912 | | 9 | | 150, 152-157 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 32

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 285B | 24 | PW | DY | | 5-0 | 77-12-11 | D05308J | | | | 4 | | TB0318Y | A018 | BJ | 050-099, 162-199, 277-299 |
| 285B | 24 | PW | DY | | 5-0 | 77-12-11 | D05433J | | | | 12 | | TB0272Y | A026 | BJ | 150-157, 275-276 |
| 285R | 24 | PW | DY | | 0-0 | 77-12-11 | D05308J | | | | 5 | | TB0318Y | A017 | BJ | 050-099, 162-199, 277-299 |
| 285R | 24 | PW | DY | | 0-0 | 77-12-11 | D05433J | | | | 11 | | TB0272Y | A025 | BJ | 150-157, 275-276 |
| 285Z | | | DY | | 0-0 | 77-12-11 | D05308J | | | | 3 | | TB0318Y | C017 | BJ | 050-099, 162-199, 277-299 |
| 285Z | | | DY | | 0-0 | 77-12-11 | D05433J | | | | 9 | | TB0272Y | C025 | BJ | 150-157, 275-276 |
| 287B | 24 | PW | EP | | 5-0 | 77-12-11 | D06582J | | | | 23 | | TB0318Y | A018 | BJ | 050-099 |
| 287B | 24 | PW | DI | | 5-0 | 77-12-11 | D06582J | | | | 23 | | TB0272Y | A026 | BJ | 150-157, 275-276 |
| 287B | 24 | PW | DI | | 5-0 | 77-12-11 | D06582J | | | | 23 | | TB0318Y | A018 | BJ | 162-199, 277-299 |
| 287R | 24 | PW | EP | | 0-0 | 77-12-11 | D06582J | | | | 22 | | TB0318Y | A017 | BJ | 050-099 |
| 287R | 24 | PW | DI | | 0-0 | 77-12-11 | D06582J | | | | 22 | | TB0272Y | A025 | BJ | 150-157, 275-276 |
| 287R | 24 | PW | DI | | 0-0 | 77-12-11 | D06582J | | | | 22 | | TB0318Y | A017 | BJ | 162-199, 277-299 |
| 287Z | | | EP | | 0-0 | 77-12-11 | D06582J | | | | 24 | | TB0318Y | C017 | BJ | 050-099 |
| 287Z | | | DI | | 0-0 | 77-12-11 | D06582J | | | | 24 | | TB0272Y | C025 | BJ | 150-157, 275-276 |
| 287Z | | | DI | | 0-0 | 77-12-11 | D06582J | | | | 24 | | TB0318Y | C017 | BJ | 162-199, 277-299 |
| 288 | 24 | PK | | | 5-0 | 21-61-21 | D05658J | | | | 35 | | TB0272Z | 17 | BJ | ALL |
| 28A | 20 | PA | | | 3-0 | 21-66-11 | GDX0004 | | | D.. | 2 | | D02912 | 11 | | 050-099, 162-199 |
| 28A | 20 | PA | | | 3-0 | 21-66-41 | GDX0004 | | | D.. | 2 | | D02912 | 11 | | 150, 152-157 |
| 28E | 20 | UA | | | 7-0 | 21-66-21 | TB0318X | | | | | | GDX0008 | S.. | 2 | 050-099 |
| 28E | 20 | PA | | | 7-0 | 21-66-21 | TB0318X | | | | | | GDX0008 | S.. | 2 | 162-199 |
| 294B | 24 | PL | EH | | 8-0 | 21-61-51 | D13400 | | | | A3 | | D04906J | 25 | | 050-099 |
| 294B | 24 | PL | BH | | 7-0 | 21-61-51 | D04906J | | | | 25 | | D13400 | A3 | | 150-199, 275-299 |
| 294R | 24 | PL | EH | | 0-0 | 21-61-51 | D13400 | | | | B3 | | D04906J | 26 | | 050-099 |
| 294R | 24 | PL | BH | | 0-0 | 21-61-51 | D04906J | | | | 26 | | D13400 | B3 | | 150-199, 275-299 |
| 297B | 24 | PL | EI | | 8-0 | 21-61-51 | D13400 | | | | A2 | | D04906J | 28 | | 050-099 |
| 297B | 24 | PL | BN | | 7-0 | 21-61-51 | D04906J | | | | 28 | | D13400 | A2 | | 150-199, 275-299 |
| 297R | 24 | PL | EI | | 0-0 | 21-61-51 | D13400 | | | | B2 | | D04906J | 27 | | 050-099 |
| 297R | 24 | PL | BN | | 0-0 | 21-61-51 | D04906J | | | | 27 | | D13400 | B2 | | 150-199, 275-299 |
| 29A | 22 | PA | | | 6-0 | 21-66-11 | TB0302Y | | | | C027 | BJ | SP04058 | | W | 050-099 |
| 29A | 22 | PA | | | 8-0 | 21-66-11 | TB0302Y | | | | C027 | BJ | SP04058 | | W | 162-199 |
| 29E | 22 | PA | | | 4-0 | 21-66-31 | D06934J | | | | 19 | | TB0222X | D013 | BJ | 050-099, 150, 152-199 |
| 306B | 24 | PX | MF | | 3-0 | 73-31-11 | D05308J | | | | 31 | | D05306J | 31 | | 050-099 |
| 306B | 24 | PX | CL | | 3-0 | 73-31-11 | D05308J | | | | 31 | | D05306J | 31 | | 150-199, 275-299 |
| 306R | 24 | PX | MF | | 0-0 | 73-31-11 | D05308J | | | | 30 | | D05306J | 33 | | 050-099 |
| 306R | 24 | PX | CL | | 0-0 | 73-31-11 | D05308J | | | | 30 | | D05306J | 33 | | 150-199, 275-299 |
| 306Y | 24 | PX | MF | | 0-0 | 73-31-11 | D05308J | | | | 32 | | D05306J | 34 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0170
Page 33
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 306Y | 24 | PX | CL | 0-0 | 73-31-11 | D05308J | | 32 | | | | | D05306J | 34 | | | 150-199, 275-299 |
| 306Z | | | MF | 0-0 | 73-31-11 | D05308J | | 29 | | | | | D05306J | 13 | | | 050-099 |
| 306Z | | | CL | 0-0 | 73-31-11 | D05308J | | 29 | | | | | D05306J | 13 | | | 150-199, 275-299 |
| 307B | 24 | PX | MG | 4-0 | 36-23-11 | D04802J | | 37 | | | | | D05780J | 18 | | | 050-099 |
| 307B | 24 | PX | S | 4-0 | 36-23-11 | D04802J | | 37 | | | | | D05780J | 18 | | | 150-199, 275-299 |
| 307R | 24 | PX | MG | 0-0 | 36-23-11 | D04802J | | 38 | | | | | D05780J | 19 | | | 050-099 |
| 307R | 24 | PX | S | 0-0 | 36-23-11 | D04802J | | 38 | | | | | D05780J | 19 | | | 150-199, 275-299 |
| 307Y | 24 | PX | MG | 0-0 | 36-23-11 | D04802J | | 39 | | | | | D05780J | 20 | | | 050-099 |
| 307Y | 24 | PX | S | 0-0 | 36-23-11 | D04802J | | 39 | | | | | D05780J | 20 | | | 150-199, 275-299 |
| 307Z | | | MG | 0-0 | 36-23-11 | D04802J | | 36 | | | | | D05780J | 17 | | | 050-099 |
| 307Z | | | S | 0-0 | 36-23-11 | D04802J | | 36 | | | | | D05780J | 17 | | | 150-199, 275-299 |
| 30A | 22 | PA | | 7-0 | 21-66-11 | TB0302Y | | C027 | BJ | | | | D13848 | X1 | | | 050-099 |
| 30A | 22 | PA | | 9-0 | 21-66-11 | TB0302Y | | C027 | BJ | | | | D13848 | X1 | | | 162-199 |
| 30B | 24 | PK | | 10-0 | 21-45-21 | D05658J | | 40 | | | | | TB0216Y | C012 | BJ | | 275-299 |
| 30C | 24 | PK | | 10-0 | 21-45-21 | D05658J | | 41 | | | | | TB0074Y | C014 | BJ | | 275-299 |
| 314B | 24 | PM | CU | 3-0 | 79-31-11 | D05306J | | 41 | | | | | D05360J | 31 | | | ALL |
| 314R | 24 | PM | CU | 0-0 | 79-31-11 | D05306J | | 40 | | | | | D05360J | 30 | | | ALL |
| 314Y | 24 | PM | CU | 0-0 | 79-31-11 | D05306J | | 39 | | | | | D05360J | 32 | | | ALL |
| 31A | 22 | PA | | 8-0 | 21-66-11 | TB0302Y | | C027 | BJ | | | | D13846 | X1 | | | 050-099, 162-199 |
| 31E | 20 | PA | | 4-0 | 21-66-31 | D06934J | | 20 | | | | | TB0222X | A018 | BJ | | 050-099, 150, 152-199 |
| 327 | 24 | PK | | 6-0 | 24-11-11 | D05360J | | 13 | | | | | TB0302R | C033 | 2 | | 050, 150, 152-199 |
| 327 | 24 | PK | | 6-0 | 24-11-11 | D05360J | | 13 | | | | | TB0302R | C033 | 2 | * | 151 |
| 32A | 20 | PA | | 8-0 | 21-66-11 | D13846 | | A2 | | | | | TB0318X | B035 | BJ | | 050-099, 162-199 |
| 32E | 20 | PA | | 4-0 | 21-66-31 | D06934J | | 21 | | | | | TB0222X | D017 | BJ | | 050-099, 150, 152-199 |
| 33A | 20 | PA | | 8-0 | 21-66-11 | D13846 | | B2 | | | | | TB0318X | C035 | BJ | | 050-099, 162-199 |
| 33E | 20 | PA | | 4-0 | 21-66-31 | D06934J | | 22 | | | | | TB0222X | C017 | BJ | | 050-099, 150, 152-199 |
| 341 | 24 | PK | | 10-0 | 24-11-11 | D11654 | | 6 | | | | | TB0302R | A033 | 2 | | 050, 150, 152-199 |
| 341 | 24 | PK | | 10-0 | 24-11-11 | D11654 | | 6 | | | | | TB0302R | A033 | 2 | * | 151 |
| 34A | 20 | PA | | 8-0 | 21-66-11 | D13846 | | C2 | | | | | TB0318X | D035 | BJ | | 050-099, 162-199 |
| 34E | 22 | PA | | 5-0 | 21-66-31 | D06934J | | 23 | | | | | TB0318Z | 32 | BJ | | 050-099, 150, 152-199 |
| 35A | 20 | PA | | 8-0 | 21-66-11 | D13846 | | X2 | | | | | TB0302Y | A028 | BJ | | 050-099, 162-199 |
| 35E | 22 | PA | | 4-0 | 21-66-31 | D06934J | | 25 | | | | | D04672J | 30 | | | 050-099, 150, 152-199 |
| 36A | 20 | PA | | 7-0 | 21-66-11 | D13846 | | A1 | | | | | D06934J | 6 | | | 050-099, 162-199 |
| 36E | 22 | PA | | 5-0 | 21-66-31 | D06934J | | 24 | | | | | D13852 | X2 | | | 050-099, 150, 152-199 |
| 37A | 20 | PA | | 7-0 | 21-66-11 | D13846 | | B1 | | | | | D06934J | 7 | | | 050-099, 162-199 |
| 37E | 20 | PA | | 5-0 | 21-66-31 | D06934J | | 26 | | | | | D13852 | A1 | | | 050-099, 150, 152-199 |
| 38A | 20 | PA | | 14-0 | 21-66-11 | D13846 | | C1 | | | | | D06934J | 8 | | | 050-099, 162-199 |
| 38E | 20 | PA | | 14-0 | 21-66-31 | D06934J | | 27 | | | | | D13852 | B1 | | | 050-099, 162 |
| 38E | 20 | PA | | 7-0 | 21-66-31 | D13852 | | B1 | | | | | D06934J | 27 | | | 150, 152-157 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 34

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 38E | 20 | PA | | | 16-0 | 21-66-31 | D06934J | | 27 | | D13852 | B1 | | | 163-199 |
| 39A | 22 | PA | | | 14-0 | 21-66-11 | C00400 | | C1 | D | D13840 | A2 | | | 050-099 |
| 39A | 22 | PA | | | 14-0 | 21-66-11 | C00400 | | C1 | D | D13840 | A2 | | | 162-163 |
| 39A | 22 | PA | | | 7-0 | 21-66-11 | TB0318X | | C012 | BJ | D13840 | A2 | | | 164-199 |
| 39FB | 22 | PR | FG | | 5-0 | 21-66-11 | D06934J | | 34 | | TB0318X | A010 | BJ | | 050-099 |
| 39FB | 22 | PR | EL | | 5-0 | 21-66-11 | D06934J | | 34 | | TB0318X | A010 | BJ | | 162-199 |
| 39FR | 22 | PR | FG | | 0-0 | 21-66-11 | D06934J | | 35 | | TB0318X | A009 | BJ | | 050-099 |
| 39FR | 22 | PR | EL | | 0-0 | 21-66-11 | D06934J | | 35 | | TB0318X | A009 | BJ | | 162-199 |
| 39FZ | | | FG | | 0-0 | 21-66-11 | D06934J | | 36 | | TB0318X | | | FV | 050-099 |
| 39FZ | | | EL | | 0-0 | 21-66-11 | D06934J | | 36 | | TB0318X | | | FV | 162-199 |
| 401B | 24 | PN | AC | | 5-0 | 27-51-41 | D05300J | | 26 | | TB0302X | A004 | BJ | | ALL |
| 401G | 24 | PN | AC | | 0-0 | 27-51-41 | D05300J | | 29 | | TB0302X | D004 | BJ | | ALL |
| 401R | 24 | PN | AC | | 0-0 | 27-51-41 | D05300J | | 27 | | TB0302X | B004 | BJ | | ALL |
| 401Y | 24 | PN | AC | | 0-0 | 27-51-41 | D05300J | | 28 | | TB0302X | C004 | BJ | | ALL |
| 40A | 20 | PA | | | 7-0 | 21-66-11 | SP04060 | | | W | GDX0008 | D.. | 2 | | 050-099 |
| 40A | 20 | PA | | | 9-0 | 21-66-11 | SP04060 | | | W | GDX0008 | D.. | 2 | | 162-199 |
| 40E | 22 | PA | | | 5-0 | 21-66-31 | D06934J | | 28 | | SP04080 | | W | | 050-099, 150, 152-199 |
| 40FB | 22 | PR | FC | | 5-0 | 21-66-21 | D05060J | | 13 | | TB0318X | B010 | BJ | | 050-099, 162-199 |
| 40FR | 22 | PR | FC | | 0-0 | 21-66-21 | D05060J | | 12 | | TB0318X | B009 | BJ | | 050-099, 162-199 |
| 40FZ | | | FC | | 0-0 | 21-66-21 | D05060J | | 14 | | TB0318X | | | FW | 050-099, 162-199 |
| 41E | 20 | PA | | | 4-0 | 21-66-31 | D06934J | | 29 | | TB0222X | B018 | BJ | | 050-099, 150, 152-199 |
| 41F | 22 | PA | | | 4-0 | 21-66-21 | D04672J | | 15 | | TB0318Z | 32 | BJ | | 050-099, 162-199 |
| 41FB | 22 | PR | EW | | 5-0 | 21-66-41 | TB0318X | | D010 | BJ | D05060J | 17 | | | 050-099 |
| 41FB | 22 | PR | HA | | 5-0 | 21-66-41 | TB0318X | | D010 | BJ | D05060J | 17 | | | 150, 152-199 |
| 41FR | 22 | PR | EW | | 0-0 | 21-66-41 | TB0318X | | D009 | BJ | D05060J | 16 | | | 050-099 |
| 41FR | 22 | PR | HA | | 0-0 | 21-66-41 | TB0318X | | D009 | BJ | D05060J | 16 | | | 150, 152-199 |
| 41FZ | | | EW | | 0-0 | 21-66-41 | D05060J | | 18 | | TB0318X | | | GB | 050-099 |
| 41FZ | | | HA | | 0-0 | 21-66-41 | D05060J | | 18 | | TB0318X | | | GB | 150, 152-199 |
| 42A | 22 | PA | | | 5-0 | 21-66-11 | SP04064 | | | W | D06934J | 9 | | | 050-099 |
| 42A | 22 | PA | | | 7-0 | 21-66-11 | SP04064 | | | W | D06934J | 9 | | | 162-199 |
| 42F | 20 | UA | | | 7-0 | 21-66-11 | GDX0008 | | S.. | 2 | TB0318X | | | FV | 050-099, 162-199 |
| 43A | 22 | PA | | | 10-0 | 21-66-11 | D13844 | | B2 | | D13840 | X2 | | | 050-099 |
| 43A | 22 | PA | | | 9-0 | 21-66-11 | D13844 | | B2 | | D13840 | X2 | | | 162-199 |
| 43EB | 22 | PR | EY | | 5-0 | 21-66-31 | D06934J | | 31 | | TB0318X | C010 | BJ | | 050-099 |
| 43EB | 22 | PR | HB | | 5-0 | 21-66-31 | D06934J | | 31 | | TB0318X | C010 | BJ | | 150, 152-199 |
| 43ER | 22 | PR | EY | | 0-0 | 21-66-31 | D06934J | | 30 | | TB0318X | C009 | BJ | | 050-099 |
| 43ER | 22 | PR | HB | | 0-0 | 21-66-31 | D06934J | | 30 | | TB0318X | C009 | BJ | | 150, 152-199 |
| 43EZ | | | EY | | 0-0 | 21-66-31 | D06934J | | 32 | | TB0318X | | | FX | 050-099 |
| 43EZ | | | HB | | 0-0 | 21-66-31 | D06934J | | 32 | | TB0318X | | | FX | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 35

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 43F | 20 | | UA | 7-0 | 21-66-41 | GDX0008 | S.. | 2 | | TB0318X | | | | GB | 050-099, 150, 152-157, 167-199 | |
| 43F | 20 | | PA | 7-0 | 21-66-41 | GDX0008 | S.. | 2 | | TB0318X | | | | GB | 162-166 | |
| 44A | 22 | | PA | 10-0 | 21-66-11 | TB0076Z | | 13 | BJ | D13840 | | X1 | | | 050-099, 162-199 | |
| 44C | 22 | | PA | 5-0 | 21-66-41 | TB0318D | C008 | 2 | | TB0318D | | C007 | 2 | | 150, 152-157 | |
| 44E | 22 | | PA | 5-0 | 21-66-31 | D06934J | | 33 | | TB0318D | | A007 | 2 | | 050-099, 150, 152-199 | |
| 44F | 22 | | PA | 5-0 | 21-66-41 | TB0318D | A008 | 2 | | D05060J | | 19 | | | 050-099, 150, 152-199 | |
| 45A | 20 | | PA | 7-0 | 21-66-11 | SP04062 | | | W | GDX0008 | | D.. | 2 | | 050-099 | |
| 45A | 20 | | PA | 9-0 | 21-66-11 | SP04062 | | | W | GDX0008 | | D.. | 2 | | 162-199 | |
| 45E | 22 | | PA | 7-0 | 21-66-31 | TB0318X | A036 | | BJ | D13852 | | X1 | | | 050-099, 150, 152-199 | |
| 45F | 22 | | PA | 7-0 | 36-11-61 | D04662J | | 10 | | TB0218Y | | C013 | BJ | | 050-099, 150-155, 162-165, 275-276 | |
| 45F | 22 | | PA | 5-0 | 36-11-61 | D04662J | | 10 | | TB0218Y | | C013 | BJ | | 156-157, 166-199, 277-299 | |
| 46A | 22 | | PA | 5-0 | 21-66-11 | TB0302Y | A028 | | BJ | D06934J | | 10 | | | 050-099, 162-199 | |
| 46E | 20 | | PA | 4-0 | 21-66-31 | TB0222X | D018 | | BJ | D13852 | | A2 | | | 050-099, 150, 152-199 | |
| 46F | 22 | | PA | 7-0 | 36-11-61 | D04662J | | 8 | | TB0220Y | | A002 | BJ | | 050-099, 150-155, 162-165, 275-276 | |
| 46F | 22 | | PA | 5-0 | 36-11-61 | D04662J | | 8 | | TB0220Y | | A002 | BJ | | 156-157, 166-199, 277-299 | |
| 47A | 22 | | PA | 8-0 | 21-66-11 | TB0302Y | A028 | | BJ | D11798 | | 10 | | | 050-099, 162-199 | |
| 47E | 20 | | PA | 4-0 | 21-66-31 | TB0222X | C018 | | BJ | D13852 | | B2 | | | 050-099, 150, 152-199 | |
| 47F | 22 | | PA | 7-0 | 36-11-61 | D04662J | | 11 | | TB0260D | | C008 | 2 | | 050-099, 150-155, 162-165, 275-276 | |
| 47F | 22 | | PA | 6-0 | 36-11-61 | D04662J | | 11 | | TB0260D | | C008 | 2 | | 156, 166 | |
| 47F | 22 | | PA | 6-0 | 36-11-61 | D04662J | | 11 | | TB0318Y | | C015 | BJ | | 157, 167-199, 277-299 | |
| 48A | 22 | | PA | 6-0 | 21-66-11 | D11798 | | 11 | | D13848 | | A2 | | | 050-099 | |
| 48A | 22 | | PA | 11-0 | 21-66-11 | D11798 | | 11 | | D13848 | | A2 | | | 162-199 | |
| 48E | 20 | | PA | 7-0 | 21-66-31 | GDX0008 | D.. | 2 | | SP04076 | | | W | | 050-099 | |
| 48E | 20 | | PA | 9-0 | 21-66-31 | GDX0008 | D.. | 2 | | SP04076 | | | W | | 150, 152-199 | |
| 48F | 22 | | PA | 6-0 | 36-11-61 | D05308J | | 41 | | TB0318Y | | C015 | BJ | | 157, 167-199, 277-299 | |
| 49A | 22 | | PA | 6-0 | 21-66-11 | D13848 | | A3 | | TB0318D | | A005 | 2 | | 050-099 | |
| 49A | 22 | | PA | 9-0 | 21-66-11 | D13848 | | A3 | | TB0318D | | A005 | 2 | | 162-199 | |
| 49E | 20 | | PA | 7-0 | 21-66-31 | GDX0009 | D.. | 2 | | SP04078 | | | W | | 050-099 | |
| 49E | 20 | | PA | 9-0 | 21-66-31 | GDX0009 | D.. | 2 | | SP04078 | | | W | | 150, 152-199 | |
| 49F | 22 | | PA | 7-0 | 36-11-61 | D05308J | | 40 | | TB0218Y | | C013 | BJ | | 050-099, 275-276 | |
| 49F | 22 | | PA | 6-0 | 36-11-61 | D05308J | | 40 | | TB0218Y | | C013 | BJ | | 150-155, 162-165 | |
| 49F | 22 | | PA | 5-0 | 36-11-61 | D05308J | | 40 | | TB0218Y | | C013 | BJ | | 156-157, 166-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 36

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 501 | 24 | | PK | 6-0 | 21-58-16 | D10890 | | X1 | | | | | TB0260Z | 2 | BJ | | 050-099, 155-199, 276-299 |
| 501 | 24 | | PK | 5-0 | 21-58-16 | D10890 | | X1 | | | | | TB0252Y | C001 | BJ | | 150-154, 275 |
| 502 | 24 | | PK | 6-0 | 21-58-16 | D10890 | | A2 | | | | | D04662J | 23 | | | 050-099, 275-299 |
| 502 | 24 | | PK | 5-0 | 21-58-16 | D10890 | | A2 | | | | | D04662J | 23 | | | 150-199 |
| 503 | 24 | | PK | 6-0 | 36-11-11 | D04904J | | 54 | | | | | D03474 | X2 | | | ALL |
| 504 | 24 | | PK | 7-0 | 21-58-14 | K00343 | | X1 | C | | | | TB0218Y | A010 | BJ | | 050-099, 275-299 |
| 504 | 24 | | PK | 6-0 | 21-58-14 | K00343 | | X1 | C | | | | TB0218Y | A010 | BJ | | 150-199 |
| 506 | 24 | | PK | 10-0 | 21-58-14 | K00343 | | X2 | C | | | | D04904J | 30 | | | 050-099, 275-299 |
| 506 | 24 | | PK | 6-0 | 21-58-14 | K00343 | | X2 | C | | | | D04904J | 30 | | | 150-199 |
| 508 | 24 | | PK | 7-0 | 21-58-14 | SP01608 | | | W | | | | D04904J | 32 | | | 050-099, 275-299 |
| 508 | 24 | | PK | 6-0 | 21-58-14 | SP01608 | | | W | | | | D04904J | 32 | | | 150-199 |
| 509 | 24 | | PK | 5-0 | 22-32-15 | D03610 | | 10 | | | | | D05433J | 7 | | | ALL |
| 510 | 24 | | PK | 5-0 | 22-32-15 | D03610 | | 11 | | | | | D05433J | 8 | | | ALL |
| 511 | 22 | | PA | 6-0 | 22-14-31 | D03614 | | 1 | | | | | TB0076Y | A006 | BJ | | ALL |
| 512 | 22 | | PA | 6-0 | 22-14-31 | D03614 | | 5 | | | | | TB0076Y | A006 | BJ | | ALL |
| 513 | 22 | | PA | 6-0 | 22-14-31 | D03614 | | 7 | | | | | TB0076Y | C006 | BJ | | ALL |
| 514 | 22 | | PA | 6-0 | 22-14-31 | D03614 | | 11 | | | | | TB0076Y | C006 | BJ | | ALL |
| 515 | 20 | | PA | 3-0 | 22-14-31 | GDX0006 | | D.. | 2 | | | | D03614 | 2 | | | ALL |
| 516 | 20 | | PA | 3-0 | 22-14-31 | GDX0006 | | D.. | 2 | | | | D03614 | 4 | | | ALL |
| 517 | 20 | | PA | 3-0 | 22-14-31 | GDX0006 | | D.. | 2 | | | | D03614 | 8 | | | ALL |
| 518 | 20 | | PA | 3-0 | 22-14-31 | GDX0006 | | D.. | 2 | | | | D03614 | 10 | | | ALL |
| 519 | 24 | | PK | 3-0 | 32-09-11 | D01736 | | A2 | | | | | TB0074Z | 5 | BJ | | ALL |
| 51D | 24 | | PK | 7-0 | SPARE | D10950 | | B2 | | | | | D05300J | 34 | | | 157, 167-199 |
| 51D | 24 | | PK | 6-0 | SPARE | D10950 | | B2 | | | | | D05300J | 34 | | | 277-299 |
| 51F | 24 | | PK | 10-0 | 21-58-12 | D11808 | | 7 | | | | | TB0080Y | A006 | BJ | | 050-099, 150-154, 275-299 |
| 51F | 24 | | PV | FD | 21-58-12 | D11808 | | 7 | | | | | TB0080Y | A006 | BJ | | 155-199 |
| 51FZ | | | | FD | 21-58-12 | D11808 | | DED | | | | | TB0080Y | DED | | | 155-199 |
| 51G | 24 | | PK | 5-0 | 21-58-12 | D11808 | | 3 | | | | | D04662J | 15 | | | 050-099, 150-154, 275-299 |
| 51G | 24 | | PV | FE | 21-58-12 | D11808 | | 3 | | | | | D04662J | 15 | | | 155-199 |
| 51GZ | | | | FE | 21-58-12 | D11808 | | DED | | | | | D04662J | DED | | | 155-199 |
| 51H | 24 | | PK | 5-0 | 21-58-12 | D11808 | | 2 | | | | | D04662J | 16 | | | ALL |
| 51J | 20 | | PA | 6-0 | 21-58-12 | D11808 | | 4 | | | | | GDX0015 | D.. | 2 | | ALL |
| 51K | 24 | | PK | 8-0 | 21-58-12 | D03586 | | C2 | | | | | TB0218Y | A013 | BJ | | ALL |
| 51L | 24 | | PK | 9-0 | 21-58-12 | D03586 | | C1 | | | | | TB0272Y | C032 | BJ | | ALL |
| 51M | 24 | | PK | 9-0 | 21-58-12 | D03586 | | C3 | | | | | TB0272F | C015 | 2 | | 050-099, 275-299 |
| 51M | 24 | | PK | 8-0 | 21-58-12 | D03586 | | C3 | | | | | TB0272F | C015 | 2 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 37

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 51N | 24 | | PK | 9-0 | 21-58-12 | D04802J | | 13 | | | | TB0272F | A015 | 2 | | 050-099, 275-299 |
| 51N | 24 | | PK | 5-0 | 21-58-12 | D04802J | | 13 | | | | TB0272F | A015 | 2 | | 150-199 |
| 51P | 24 | | PV | GX | 12-0 | 32-09-11 | D20090 | | X1 | | | TB0218Y | C008 | BJ | | ALL |
| 51PZ | | | | GX | 0-0 | 32-09-11 | D20090 | | DED | | | TB0218Y | DED | | | ALL |
| 51Q | 24 | | PV | HQ | 12-0 | 32-09-11 | D20090 | | X2 | | | TB0074Z | | 4 | BJ | 050-099, 150-156, 162-199, 275-299 |
| 51Q | 24 | | PK | | 12-0 | 32-09-11 | D20090 | | X2 | | | TB0074Z | | 4 | BJ | 157 |
| 51QZ | | | | HQ | 0-0 | 32-09-11 | D20090 | | DED | | | TB0074Z | DED | | | 050-099, 150-156, 162-199, 275-299 |
| 51R | 24 | | PV | HR | 12-0 | 32-09-11 | D20092 | | X2 | | | TB0074Z | | 4 | BJ | 050-099, 150-156, 162-199, 275-299 |
| 51R | 24 | | PK | | 12-0 | 32-09-11 | D20092 | | X2 | | | TB0074Z | | 4 | BJ | 157 |
| 51RZ | | | | HR | 0-0 | 32-09-11 | D20092 | | DED | | | TB0074Z | DED | | | 050-099, 150-156, 162-199, 275-299 |
| 51U | 24 | | PV | GY | 12-0 | 32-09-11 | D20092 | | X1 | | | TB0218Y | C008 | BJ | | ALL |
| 51UZ | | | | GY | 0-0 | 32-09-11 | D20092 | | DED | | | TB0218Y | DED | | | ALL |
| 51W | 24 | | PV | GV | 4-0 | 32-09-11 | TB0218Y | | C008 | BJ | | TB0216Z | | 13 | BJ | ALL |
| 51WZ | | | | GV | 0-0 | 32-09-11 | TB0218Y | | DED | | | TB0216Z | DED | | | ALL |
| 520 | 24 | | PK | | 5-0 | 21-58-16 | D10890 | | X2 | | | TB0252D | A004 | 2 | | 050-099, 275-299 |
| 520 | 24 | | PK | | 3-0 | 21-58-16 | D10890 | | X2 | | | TB0252D | A004 | 2 | | 150-199 |
| 522 | 24 | | PK | | 5-0 | 21-25-11 | D04672J | | 32 | | | TB0220Y | A012 | BJ | | ALL |
| 523 | 22 | | PA | | 5-0 | 21-25-11 | D04672J | | 33 | | | TB0220Y | C019 | BJ | | ALL |
| 524 | 24 | | PK | | 5-0 | 21-25-11 | D04672J | | 36 | | | TB0220Y | A012 | BJ | | ALL |
| 525 | 24 | | PK | | 6-0 | 21-25-11 | D04672J | | 37 | | | K00415 | | X2 | C | ALL |
| 526 | 24 | | PK | | 9-0 | 21-25-11 | TB0074Y | | C013 | BJ | | SP01596 | | | W | ALL |
| 527 | 20 | | PA | | 3-0 | 21-25-11 | SP01598 | | | W | | GDX0008 | | D.. | 2 | ALL |
| 528 | 24 | | PV | BW | 6-0 | 32-09-11 | D04672J | | 24 | | | TB0216Z | | 13 | BJ | ALL |
| 528Z | | | | BW | 0-0 | 32-09-11 | D04672J | | DED | | | TB0216Z | DED | | | ALL |
| 529 | 24 | | PK | | 5-0 | 21-25-11 | K00415 | | X1 | C | | TB0220Y | A012 | BJ | | ALL |
| 530 | 24 | | PK | | 6-0 | 36-11-61 | D04662J | | 48 | | | TB0272G | 42 | 2 | | 050-099 |
| 530 | 24 | | PK | | 6-0 | 36-11-61 | D04662J | | 48 | | | TB0260Y | A005 | BJ | | 150-154, 275 |
| 530 | 24 | | PK | | 7-0 | 36-11-61 | D04662J | | 48 | | | TB0272G | 42 | 2 | | 155-156, 162-166, 276 |
| 530 | 24 | | PK | | 6-0 | 36-11-61 | D04662J | | 48 | | | TB0260Y | A006 | BJ | | 157, 167-199, 277-299 |
| 531 | 24 | | PK | | 6-0 | 32-09-11 | D04802J | | 11 | | | M01162 | | B | C | ALL |
| 532 | 24 | | PK | | 5-0 | 36-21-11 | D05658J | | 37 | | | TB0216Y | A018 | BJ | | 050-099, 156-157, 166-199, 277-299 |
| 532 | 24 | | PK | | 4-0 | 36-21-11 | D05658J | | 37 | | | D04904J | | 11 | | 150-155, 163-165 |
| 532 | 24 | | PK | | 4-0 | 36-21-11 | D05658J | | 37 | | | TB0216Y | A018 | BJ | | 162 |
| 532 | 24 | | PK | | 5-0 | 36-21-11 | D05658J | | 37 | | | D04904J | | 11 | | 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0176

Page 38

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 534 | 24 | | PK | | 6-0 | 21-58-16 | TB0252D | C004 | 2 | | D04662J | 25 | | | 050-099, 275-299 |
| 534 | 24 | | PK | | 5-0 | 21-58-16 | TB0252D | C004 | 2 | | D04662J | 25 | | | 150-199 |
| 535 | 24 | | PK | | 3-0 | 36-11-51 | D05658J | | 26 | | D04932J | 1 | | | ALL |
| 536 | 20 | | PA | | 7-0 | 36-11-51 | D05658J | | 27 | | TB0252Z | 11 | BJ | | 050-099 |
| 536 | 20 | | PA | | 8-0 | 36-11-51 | D05658J | | 27 | DL | TB0252Z | 11 | BJ | | 150-154, 275 |
| 536 | 20 | | PA | | 6-0 | 36-11-51 | D05658J | | 27 | | TB0252Z | 11 | BJ | | 155, 162-165, 276 |
| 537 | 24 | | PK | | 3-0 | 36-11-51 | D05658J | | 28 | | D04932J | 22 | | | ALL |
| 538 | 24 | | PK | | 3-0 | 36-11-51 | D05658J | | 30 | | D04932J | 53 | | | ALL |
| 539 | 22 | | PA | | 7-0 | 36-11-51 | D05658J | | 31 | DL | TB0252Y | A009 | BJ | | 050-099 |
| 539 | 22 | | PA | | 7-0 | 36-11-51 | D05658J | | 31 | | TB0252Y | A009 | BJ | | 150-156, 162-166, 275-276 |
| 539 | 22 | | PA | | 4-0 | 36-11-51 | D05658J | | 31 | | TB0252Y | A009 | BJ | | 157, 277-299 |
| 539 | 22 | | PA | | 5-0 | 36-11-51 | D05658J | | 31 | | TB0252Y | A009 | BJ | | 167-199 |
| 53A | 22 | | PQ | EO | 7-0 | 28-42-13 | D12156 | | A1 | | D05780J | 41 | | | 050-099 |
| 53A | 22 | | PQ | FN | 6-0 | 28-42-13 | D05780J | | 41 | | D12156 | A1 | | | 155-199, 276-299 |
| 53AZ | | | | EO | 0-0 | 28-42-13 | D12156 | DED | | | D05780J | DED | | | 050-099 |
| 53AZ | | | | FN | 0-0 | 28-42-13 | D05780J | DED | | | D12156 | DED | | | 155-199, 276-299 |
| 53B | 22 | | PQ | EE | 8-0 | 28-42-13 | D12156 | | A2 | | TB0218Y | C009 | BJ | | 050-099 |
| 53B | 22 | | PQ | FO | 6-0 | 28-42-13 | D12156 | | A2 | | TB0218Y | C009 | BJ | | 155-199, 276-299 |
| 53BZ | | | | EE | 0-0 | 28-42-13 | D12156 | DED | | | TB0218Y | DED | | | 050-099 |
| 53BZ | | | | FO | 0-0 | 28-42-13 | D12156 | DED | | | TB0218Y | DED | | | 155-199, 276-299 |
| 53C | 22 | | PQ | DX | 20-0 | 28-42-12 | D12156 | | B1 | | TB0218Y | A005 | BJ | | 050-099, 155-199, 276-299 |
| 53CZ | | | | DX | 0-0 | 28-42-12 | D12156 | DED | | | TB0218Y | DED | | | 050-099, 155-199, 276-299 |
| 53D | 22 | | PQ | DZ | 7-0 | 28-42-12 | D12156 | | B2 | | D05894J | 13 | | | 050-099 |
| 53D | 22 | | PQ | DZ | 6-0 | 28-42-12 | D05894J | | 13 | | D12156 | B2 | | | 155-199, 276-299 |
| 53DZ | | | | DZ | 0-0 | 28-42-12 | D12156 | DED | | | D05894J | DED | | | 050-099 |
| 53DZ | | | | DZ | 0-0 | 28-42-12 | D05894J | DED | | | D12156 | DED | | | 155-199, 276-299 |
| 53E | 24 | | PK | | 20-0 | 28-22-12 | D12156 | | C1 | | TB0216Z | 19 | BJ | | 050-099, 155-157, 276-278 |
| 53E | 24 | | PK | | 20-0 | 28-22-12 | D12156 | | C1 | | TB0216Z | 14 | BJ | | 162-199, 280-299 |
| 53F | 24 | | PK | | 7-0 | 28-22-12 | D12156 | | C2 | | D05658J | 55 | | | 050-099 |
| 53F | 24 | | PK | | 6-0 | 28-22-12 | D05658J | | 55 | | D12156 | C2 | | | 155-199, 276-299 |
| 53G | 24 | | PK | | 7-0 | 28-22-12 | D12156 | | D1 | | TB0216Y | C010 | BJ | | 050-099 |
| 53G | 24 | | PK | | 6-0 | 28-22-12 | D12156 | | D1 | | TB0216Y | C010 | BJ | | 155-199, 276-299 |
| 53H | 20 | | PA | | 6-0 | 28-22-12 | D12156 | | D2 | | GDX0005 | D.. | 2 | | 050-099, 155-157, 276-299 |
| 53H | 20 | | PA | | 7-0 | 28-22-12 | D12156 | | D2 | | GDX0005 | D.. | 2 | | 162-199 |

WIRE LIST
D280T132

91-21-11
Section W0170
Page 39
Aug 05/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 53K | 22 | PQ | | ED | 5-0 | 28-42-13 | D05894J | | 11 | | TB0218Y | C009 | BJ | | 050-099 |
| 53K | 22 | PQ | | FS | 5-0 | 28-42-13 | D05894J | | 11 | | TB0218Y | C009 | BJ | | 155-199, 276-299 |
| 53KZ | | | | ED | 0-0 | 28-42-13 | D05894J | | DED | | TB0218Y | DED | | | 050-099 |
| 53KZ | | | | FS | 0-0 | 28-42-13 | D05894J | | DED | | TB0218Y | DED | | | 155-199, 276-299 |
| 540 | 22 | PA | | | 7-0 | 36-11-51 | D05658J | | 33 | | TB0252Y | C009 | BJ | | 050-099, 150-156, 162-166, 275-276 |
| 540 | 22 | PA | | | 4-0 | 36-11-51 | D05658J | | 33 | | TB0252Y | C009 | BJ | | 157, 277-299 |
| 540 | 22 | PA | | | 5-0 | 36-11-51 | D05658J | | 33 | | TB0252Y | C009 | BJ | | 167-199 |
| 541 | 24 | PK | | | 3-0 | 36-11-51 | D05658J | | 29 | | D04932J | | | 57 | ALL |
| 542 | 12 | PA | | | 7-0 | 21-58-14 | K00343 | | A2 | E | D04906J | | | 6 | 050-099, 275-299 |
| 542 | 12 | PA | | | 6-0 | 21-58-14 | K00343 | | A2 | E | D04906J | | | 6 | 150-199 |
| 544 | 24 | PK | | | 4-0 | 36-23-11 | D04802J | | 31 | | D05780J | | | 13 | ALL |
| 545 | 24 | PK | | | 4-0 | 36-23-11 | D04802J | | 32 | | D05780J | | | 14 | ALL |
| 546 | 24 | PK | | | 4-0 | 36-23-11 | D04802J | | 33 | | D05780J | | | 15 | ALL |
| 547 | 24 | PK | | | 4-0 | 36-23-11 | D04802J | | 34 | | D05780J | | | 12 | ALL |
| 548 | 24 | PK | | | 4-0 | 36-23-11 | D04802J | | 35 | | D05780J | | | 16 | ALL |
| 549 | 24 | PV | | BV | 3-0 | 32-09-11 | TB0074Z | | 4 | BJ | D01388 | | | X2 | ALL |
| 549Z | | | | BV | 0-0 | 32-09-11 | TB0074Z | | DED | | D01388 | | | DED | ALL |
| 54P | 24 | VA | | | 6-0 | 21-45-21 | D04662J | | 50 | | TB0216Y | C012 | BJ | | 150-199 |
| 54P | 24 | PK | | | 10-0 | 21-45-21 | D04662J | | 50 | | TB0216Y | C012 | BJ | | 275-277 |
| 54P | 24 | PK | | | 5-0 | 21-45-21 | D04662J | | 50 | | TB0216Y | C012 | BJ | | 278-299 |
| 550 | 24 | PK | | | 6-0 | 21-58-12 | TB0250X | | B003 | BJ | D04802J | | | 20 | ALL |
| 551 | 12 | PA | | | 7-0 | 21-58-14 | K00343 | | B2 | E | D04906J | | | 8 | 050-099, 275-299 |
| 551 | 12 | PA | | | 6-0 | 21-58-14 | K00343 | | B2 | E | D04906J | | | 8 | 150-199 |
| 552 | 12 | PA | | | 7-0 | 21-58-14 | K00343 | | C2 | E | D04906J | | | 10 | 050-099, 275-299 |
| 552 | 12 | PA | | | 6-0 | 21-58-14 | K00343 | | C2 | E | D04906J | | | 10 | 150-199 |
| 553 | 16 | PA | | | 7-0 | 23-34-15 | D04709J | | 15 | | TB5076 | | | 8 | ALL |
| 554 | 24 | PK | | | 4-0 | 21-51-11 | D04672J | | 57 | | D04932J | | | 13 | ALL |
| 555 | 24 | PK | | | 4-0 | 21-51-11 | D04672J | | 55 | | D04932J | | | 14 | ALL |
| 556 | 24 | PK | | | 4-0 | 21-51-11 | D04672J | | 54 | | D04932J | | | 16 | ALL |
| 557 | 24 | PK | | | 4-0 | 21-51-11 | D04672J | | 53 | | D04932J | | | 17 | 050-099 |
| 557 | 24 | PK | | | 5-0 | 21-51-11 | D04672J | | 53 | | TB0222Y | A019 | BJ | | 150-199 |
| 557 | 24 | PK | | | 4-0 | 21-51-11 | D04672J | | 53 | | TB0222Y | A019 | BJ | | 275-299 |
| 558 | 24 | PK | | | 4-0 | 21-51-11 | D04672J | | 52 | | D04904J | | | 1 | ALL |
| 559 | 24 | PK | | | 6-0 | 32-09-11 | D03512 | | X2 | | TB0076Z | | | 11 | 050-099, 275-277, 280-299 |
| 559 | 24 | PK | | | 3-0 | 32-09-11 | D03512 | | X2 | | TB0076Z | | | 11 | 150-199, 278 |
| 55F | 22 | PA | | | 7-0 | 36-11-61 | D05308J | | 20 | | TB0220Y | A002 | BJ | | 050-099, 275-276 |
| 55F | 22 | PA | | | 6-0 | 36-11-61 | D05308J | | 20 | | TB0220Y | A002 | BJ | | 150-155, 162-165 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 40

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0176 | 286T0176 | | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 55F | 22 | | PA | | 5-0 | 36-11-61 | D05308J | | 20 | | | | | TB0220Y | A002 | BJ | | 156-157, 166-199, 277-299 |
| 560 | 24 | | PK | | 6-0 | 32-09-11 | D03512 | | X1 | | | | | TB0074Z | 10 | BJ | | 050-099, 150-199, 275-277, 280-299 |
| 560 | 24 | | PK | | 7-0 | 32-09-11 | D03512 | | X1 | | | | | TB0074Z | 10 | BJ | | 278 |
| 561 | 24 | | PK | | 7-0 | 21-26-11 | K00347 | | X1 | C | | | | TB0260Z | 2 | BJ | | 050-099, 276-299 |
| 561 | 24 | | PK | | 6-0 | 21-26-11 | K00347 | | X1 | C | | | | TB0252Y | C001 | BJ | | 150-154, 275 |
| 561 | 24 | | PK | | 6-0 | 21-26-11 | K00347 | | X1 | C | | | | TB0260Z | 2 | BJ | | 155-199 |
| 562 | 24 | | PK | | 6-0 | 21-58-16 | D10890 | | A3 | | | | | TB0260Z | 2 | BJ | | 050-099, 155-199, 276-299 |
| 562 | 24 | | PK | | 5-0 | 21-58-16 | D10890 | | A3 | | | | | TB0252Y | C001 | BJ | | 150-154, 275 |
| 563 | 22 | | PQ | CH | 4-0 | 29-11-12 | D05780J | | 29 | | | | | TB0220X | D007 | BJ | | ALL |
| 563Z | | | | CH | 0-0 | 29-11-12 | D05780J | | DED | | | | | TB0220X | DED | | | ALL |
| 565 | 24 | | PK | | 3-0 | 27-18-11 | D05300J | | 48 | | | | | D05360J | 4 | | | 050-099, 150-154, 162-165, 275-276 |
| 567 | 24 | | PK | | 3-0 | 27-18-11 | D05300J | | 49 | | | | | D05360J | 3 | | | 050-099, 150-154, 162-165, 275-276 |
| 571 | 24 | | PK | | 3-0 | 27-18-11 | D05300J | | 51 | | | | | D05360J | 7 | | | 050-099, 150-154, 162-165, 275-276 |
| 572 | 24 | | PK | | 3-0 | 27-18-11 | D05300J | | 52 | | | | | D05360J | 8 | | | 050-099, 150-154, 162-165, 275-276 |
| 573 | 24 | | PK | | 5-0 | 27-28-13 | D05300J | | 4 | | | | | TB0302Y | A014 | BJ | | ALL |
| 574 | 24 | | PK | | 5-0 | 27-28-13 | D05300J | | 8 | | | | | TB0302Y | A014 | BJ | | ALL |
| 575 | 16 | | PA | | 7-0 | 23-34-16 | D04709J | | 19 | | | | | TB5076 | 11 | C | | ALL |
| 576 | 22 | | PA | | 4-0 | 23-34-11 | D04709J | | 6 | | | | | TB0222X | A007 | BJ | | ALL |
| 577 | 24 | | PK | | 5-0 | 27-28-13 | D05310J | | 9 | | | | | TB0302Y | A014 | BJ | | ALL |
| 578 | 24 | | PK | | 3-0 | 27-28-11 | D05300J | | 1 | | | | | D05310J | 1 | | | ALL |
| 579 | 24 | | PK | | 3-0 | 27-28-11 | D05310J | | 2 | | | | | D05360J | 35 | | | ALL |
| 57A | 24 | | PK | | 5-0 | 24-11-11 | D05832J | | 16 | | | | | D11654 | 8 | | | 050-099 |
| 57A | 24 | | PK | | 5-0 | 24-11-11 | D11654 | | 8 | | | | | D05832J | 16 | | | 150-199, 275-299 |
| 57C | 24 | | PK | | 5-0 | 24-11-11 | D05300J | | 23 | | | | | TB0302R | A033 | 2 | | 050 |
| 57C | 24 | | PK | | 5-0 | 24-11-11 | D05300J | | 23 | | | | | D11654 | 6 | | | 051-099 |
| 57C | 24 | | PK | | 5-0 | 24-11-11 | TB0302R | A033 | 2 | | | | | D05300J | 23 | | | 150, 152-199 |
| 57C | 24 | | PK | | 5-0 | 24-11-11 | TB0302R | A033 | 2 | | * | | | D05300J | 23 | | | 151 |
| 57C | 24 | | PK | | 4-0 | 24-11-11 | D05300J | | 23 | | | | | D11654 | 6 | | | 275-299 |
| 57D | 24 | | PK | | 5-0 | 24-11-11 | D05300J | | 30 | | | | | D11654 | 7 | | | 050-099 |
| 57D | 24 | | PK | | 5-0 | 24-11-11 | D11654 | | 7 | | | | | D05300J | 30 | | | 150-199, 275-299 |
| 57E | 20 | | PA | | 3-0 | 24-11-11 | GDX0017 | | D.. | 2 | | | | D11654 | 3 | | | 050-099 |
| 57E | 20 | | PA | | 3-0 | 24-11-11 | D11654 | | 3 | | | | | GDX0017 | D.. | 2 | | 150-199, 278-299 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 41

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | Effectivity | | | | |
|--------------|-----------------|----|-------|---------------------------------------|------|----------|---------|-------|------|------|--------|-------------|-------|------|------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | | Equip | Term | Type | Splice |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 57E | 20 | | UA | | 3-0 | 24-11-11 | D11654 | | 3 | | | GDX0017 | D.. | 2 | | 275-277 |
| 580 | 24 | | PK | | 3-0 | 27-28-11 | D05310J | | 3 | | | D05360J | | 36 | | ALL |
| 583 | 24 | | PK | | 4-0 | 27-38-11 | D05300J | | 31 | | | D05312J | | 1 | | ALL |
| 589 | 24 | | PK | | 7-0 | 32-09-11 | TB0076Z | | 9 | BJ | | TB0074Z | | 5 | BJ | ALL |
| 58E | 24 | | PK | | 5-0 | 36-11-61 | D01991 | | X2 | | | D10160 | CAP | Y | | 050-099, 150-156, 162-166 |
| 58E | 24 | | PK | | 5-0 | 36-11-61 | D10160 | CAP | Y | | | D01991 | X2 | | | 275-276 |
| 58G | 20 | | PQ | HT | 12-0 | 78-34-21 | D10950 | D1 | | | | D05832J | | 26 | | 050-099 |
| 58G | 20 | | PQ | HT | 12-0 | 78-34-21 | D05832J | | 26 | | | D10950 | D1 | | | 150-199, 275-299 |
| 58GZ | | | | HT | 0-0 | 78-34-21 | D10950 | DED | | | | D05832J | | | HP | 050-099 |
| 58GZ | | | | HT | 0-0 | 78-34-21 | D05832J | | | HP | | D10950 | DED | | | 150-199, 275-299 |
| 58K | 20 | | PQ | HS | 12-0 | 78-34-21 | D10950 | | D2 | | | D05832J | | 23 | | 050-099 |
| 58K | 20 | | PQ | HS | 12-0 | 78-34-21 | D05832J | | 23 | | | D10950 | D2 | | | 150-199, 275-299 |
| 58KZ | | | | HS | 0-0 | 78-34-21 | D10950 | DED | | | | D05832J | | | HP | 050-099 |
| 58KZ | | | | HS | 0-0 | 78-34-21 | D05832J | | | HP | | D10950 | DED | | | 150-199, 275-299 |
| 591 | 12 | | PA | | 7-0 | 23-34-18 | D04709J | | 23 | | | TB5076 | | 9 | C | ALL |
| 592 | 12 | | PA | | 7-0 | 23-34-18 | D04709J | | 27 | | | TB5076 | | 10 | C | ALL |
| 593 | 24 | | PK | | 5-0 | 27-38-11 | D05312J | | 6 | | | TB0302X | D003 | BJ | | ALL |
| 594 | 24 | | PK | | 3-0 | 27-38-11 | D05360J | | 44 | | | D05312J | | 8 | | 050-099, 275-299 |
| 594 | 24 | | PK | | 4-0 | 27-38-11 | D05360J | | 44 | | | D05312J | | 8 | | 150-199 |
| 595 | 24 | | PK | | 3-0 | 27-38-11 | D05360J | | 45 | | | D05312J | | 9 | | 050-099, 275-299 |
| 595 | 24 | | PK | | 4-0 | 27-38-11 | D05360J | | 45 | | | D05312J | | 9 | | 150-199 |
| 597 | 24 | | PK | | 3-0 | 27-38-11 | D05360J | | 42 | | | D05312J | | 2 | | 050-099, 275-299 |
| 597 | 24 | | PK | | 4-0 | 27-38-11 | D05360J | | 42 | | | D05312J | | 2 | | 150-199 |
| 598 | 24 | | PK | | 3-0 | 27-38-11 | D05360J | | 43 | | | D05312J | | 3 | | 050-099, 275-299 |
| 598 | 24 | | PK | | 4-0 | 27-38-11 | D05360J | | 43 | | | D05312J | | 3 | | 150-199 |
| 599 | 20 | | PA | | 3-0 | 27-13-11 | D05306J | | 22 | | | D04906J | | 13 | | ALL |
| 59G | 20 | | PQ | HD | 5-0 | 78-34-11 | D05300J | | 40 | | | D05832J | | 39 | | ALL |
| 59GZ | | | | HD | 0-0 | 78-34-11 | D05300J | | | HD | | D05832J | DED | | | ALL |
| 59H | 20 | | PQ | HE | 5-0 | 78-34-11 | D05300J | | 15 | | | D05308J | | 18 | | 050-099 |
| 59H | 20 | | PQ | HE | 5-0 | 78-34-11 | D05308J | | 18 | | | D05300J | | 15 | | 150-166, 275-276, 280-299 |
| 59H | 20 | | PQ | HE | 3-0 | 78-34-11 | D05308J | | 18 | | | D05300J | | 15 | | 167-199, 277-278 |
| 59HZ | | | | HE | 0-0 | 78-34-11 | D05308J | | | HM | | D05300J | | | HD | ALL |
| 59L | 24 | | PK | | 5-0 | 24-11-11 | D05832J | | 18 | | | D11792 | | 8 | | 050-099 |
| 59L | 24 | | PK | | 5-0 | 24-11-11 | D11792 | | 8 | | | D05832J | | 18 | | 150-199, 275-299 |
| 59M | 20 | | PA | | 2-0 | 24-11-11 | GDX0017 | D.. | 2 | | | D11792 | | 3 | | 050-099 |
| 59M | 20 | | PA | | 2-0 | 24-11-11 | D11792 | | 3 | | | GDX0017 | D.. | 2 | | 150-199, 280-299 |
| 59M | 20 | | UA | | 2-0 | 24-11-11 | D11792 | | 3 | | | GDX0017 | D.. | 2 | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 42

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | To | | | | |
|--------------|-----------------|-------------|----|---------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 59N | 24 | | PK | | 4-0 | 24-11-11 | TB0302R | C033 | 2 | | D11792 | 6 | | | 050 |
| 59N | 24 | | PK | | 4-0 | 24-11-11 | D05360J | 13 | | | D11792 | 6 | | | 051-099 |
| 59N | 24 | | PK | | 5-0 | 24-11-11 | D11792 | 6 | | | TB0302R | C033 | 2 | | 150, 152-199 |
| 59N | 24 | | PK | | 5-0 | 24-11-11 | D11792 | 6 | | | TB0302R | C033 | 2 | * | 151 |
| 59N | 24 | | PK | | 5-0 | 24-11-11 | D11792 | 6 | | | D05360J | 13 | | | 275-299 |
| 59P | 24 | | PK | | 5-0 | 24-11-11 | D05832J | 19 | | | D11792 | 7 | | | 050-099 |
| 59P | 24 | | PK | | 5-0 | 24-11-11 | D11792 | 7 | | | D05832J | 19 | | | 150-199, 275-299 |
| 59R | 24 | | PK | | 5-0 | 24-11-11 | D05832J | 17 | | | D11792 | 1 | | | 050-099 |
| 59R | 24 | | PK | | 5-0 | 24-11-11 | D11792 | 1 | | | D05832J | 17 | | | 150-199, 275-299 |
| 600 | 20 | | PA | | 3-0 | 27-13-11 | D05306J | 27 | | | D04906J | 12 | | | ALL |
| 601 | 22 | | PA | | 5-0 | 27-13-11 | D05306J | 21 | | | TB0302Y | C012 | BJ | | ALL |
| 602 | 20 | | PA | | 3-0 | 27-23-11 | D05312J | 7 | | | D05306J | 1 | | | ALL |
| 603 | 20 | | PA | | 3-0 | 27-23-11 | D05312J | 4 | | | D05306J | 15 | | | ALL |
| 604 | 22 | | PA | | 5-0 | 27-23-11 | TB0302Y | A013 | BJ | | D05306J | 16 | | | ALL |
| 615 | 20 | | PA | | 3-0 | 27-09-12 | D01388 | D1 | | | GD0004 | D.. | 2 | | ALL |
| 616 | 22 | | PA | | 5-0 | 29-32-11 | D04672J | 56 | | | TB0302Y | C014 | BJ | | ALL |
| 617 | 22 | | PA | | 5-0 | 27-09-12 | D01388 | D2 | | | D05315J | 9 | | | ALL |
| 618 | 20 | | PA | | 3-0 | 27-09-12 | D02912 | 1 | | | GD0004 | D.. | 2 | | ALL |
| 619 | 22 | | PA | | 5-0 | 23-71-11 | D04709J | 10 | | | TB0218X | D002 | BJ | | ALL |
| 620 | 22 | | PA | | 5-0 | 23-71-11 | D04709J | 9 | | | D03536 | A1 | | | ALL |
| 621 | 24 | | PK | | 5-0 | 23-31-13 | D04709J | 3 | | | TB0216X | C003 | BJ | | 050-099, 275-299 |
| 621 | 24 | | PK | | 4-0 | 23-31-13 | D04709J | 3 | | | TB0216X | C003 | BJ | | 150-199 |
| 622 | 24 | | PK | | 6-0 | 21-58-11 | D03514 | 14 | | | D04672J | 26 | | | 050-099, 275-299 |
| 622 | 24 | | PK | | 7-0 | 21-58-11 | D03514 | 14 | | | D04672J | 26 | | | 150-199 |
| 623 | 24 | | PK | | 5-0 | 23-31-13 | D04709J | 1 | | | TB0302X | D005 | BJ | | 050-099, 275-299 |
| 623 | 24 | | PK | | 4-0 | 23-31-13 | D04709J | 1 | | | TB0302X | D005 | BJ | | 150-199 |
| 624 | 24 | | PK | | 3-0 | 36-11-61 | D04662J | 40 | | | D05780J | 1 | | | ALL |
| 625 | 24 | | PK | | 3-0 | 36-11-61 | D04662J | 41 | | | D05780J | 2 | | | ALL |
| 626 | 22 | | PA | | 7-0 | 36-11-61 | D04662J | 42 | | | TB0252Y | C010 | BJ | | 050-099, 150-156, 162-166, 275-276 |
| 626 | 22 | | PA | | 4-0 | 36-11-61 | D04662J | 42 | | | TB0252Y | C010 | BJ | | 157, 167-199, 277-299 |
| 627 | 22 | | PA | | 7-0 | 36-11-61 | D04662J | 43 | | | TB0252Y | A010 | BJ | | 050-099, 150-156, 162-166, 275-276 |
| 627 | 22 | | PA | | 4-0 | 36-11-61 | D04662J | 43 | | | TB0252Y | A010 | BJ | | 157, 167-199, 277-299 |
| 628 | 24 | | PK | | 3-0 | 36-11-61 | D04662J | 44 | | | D05780J | 6 | | | ALL |
| 629 | 24 | | PK | | 3-0 | 36-11-61 | D04662J | 45 | | | D05780J | 7 | | | ALL |
| 62R | 24 | | PK | | 7-0 | 21-43-11 | D12102 | X1 | | | TB0216Y | C005 | BJ | | 050-099 |
| 62R | 24 | | PK | | 10-0 | 21-43-11 | D12102 | X1 | | | TB0216Y | C005 | BJ | | 150-199 |
| 62R | 24 | | PK | | 8-0 | 21-43-11 | D12102 | X1 | | | TB0302Y | A011 | BJ | | 275-299 |

WIRE LIST

D280T132

91-21-11
Section W0170
Page 43
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 62S | 24 | | PK | 6-0 | 21-43-11 | D12102 | | X2 | | | | | D04904J | 26 | | | 050-099 |
| 62S | 24 | | PK | 8-0 | 21-43-11 | D12102 | | X2 | | | | | D04904J | 26 | | | 150-199, 275-299 |
| 62T | 24 | | PK | 7-0 | 21-43-11 | D12102 | | A2 | | | | | TB0318X | D036 | BJ | | 050-099 |
| 62T | 24 | | PK | 10-0 | 21-43-11 | D12102 | | A2 | | | | | TB0318X | D036 | BJ | | 150-199 |
| 62T | 24 | | PK | 8-0 | 21-43-11 | D12102 | | A2 | | | | | TB0318X | D036 | BJ | | 275-299 |
| 62U | 24 | | PK | 6-0 | 21-43-11 | D12102 | | A3 | | | | | D04904J | 27 | | | 050-099 |
| 62U | 24 | | PK | 8-0 | 21-43-11 | D12102 | | A3 | | | | | D04904J | 27 | | | 150-199, 275-299 |
| 630 | 24 | | PK | 3-0 | 36-11-61 | D04662J | | 46 | | | | | D05780J | 8 | | | ALL |
| 631 | 24 | | PK | 8-0 | 21-58-12 | D04802J | | 19 | | | | | D12244 | 11 | | | 050-099 |
| 631 | 24 | | PK | 6-0 | 21-58-12 | D04802J | | 19 | | | | | TB0250D | C005 | 2 | | 150-154, 275 |
| 631 | 24 | | PK | 7-0 | 21-58-12 | D04802J | | 19 | | | | | D12244 | 11 | | | 155-199, 276-299 |
| 632 | 24 | | PK | 6-0 | 36-11-41 | TB0272D | | A022 | 2 | | | | D02886 | A2 | | | ALL |
| 633 | 24 | | PK | 6-0 | 36-11-41 | D04662J | | 2 | | | | | D02886 | A1 | | | ALL |
| 634 | 22 | | PA | 5-0 | 21-58-16 | D05360J | | 9 | | | | | TB0216Y | A016 | BJ | | 050-099, 275-299 |
| 634 | 22 | | PA | 4-0 | 21-58-16 | D05360J | | 9 | | | | | TB0216Y | A016 | BJ | | 150-199 |
| 638 | 24 | | PK | 6-0 | 21-58-12 | D02886 | | C2 | | | | | TB0252Z | 7 | BJ | | 050-099, 275-299 |
| 638 | 24 | | PK | 7-0 | 21-58-12 | D02886 | | C2 | | | | | TB0252Z | 7 | BJ | | 150-199 |
| 639 | 24 | | PK | 6-0 | 21-58-12 | D02886 | | C1 | | | | | TB0272Y | A024 | BJ | | ALL |
| 63L | 24 | | PK | 5-0 | 73-21-18 | D12246 | | 7 | | | | | TB0220Y | A001 | BJ | | 050-099, 150-154, 275-276 |
| 63L | 24 | | PK | 6-0 | 73-21-18 | D12246 | | 7 | | | | | TB0220Y | A001 | BJ | | 155-199, 277-299 |
| 63M | 24 | | PK | 6-0 | 73-21-18 | D12246 | | 3 | | | | | D05300J | 59 | | | 050-099, 150-154, 275-276 |
| 63M | 24 | | PK | 5-0 | 73-21-18 | D12246 | | 3 | | | | | D05300J | 59 | | | 155-199, 277-299 |
| 63N | 24 | | PK | 4-0 | 73-21-18 | D05300J | | 61 | | | | | TB0220Y | A001 | BJ | | ALL |
| 640 | 24 | | PK | 3-0 | 27-81-31 | D02284 | | A2 | | | | | TB0074Y | C008 | BJ | | ALL |
| 641 | 24 | | PK | 3-0 | 27-81-31 | D02284 | | X1 | | | | | TB0074Y | C008 | BJ | | ALL |
| 642 | 24 | | PK | 6-0 | 27-81-31 | D05894J | | 3 | | | | | TB0074Y | C008 | BJ | | ALL |
| 643 | 24 | | PK | 6-0 | 27-81-31 | D02284 | | X2 | | | | | D05300J | 11 | | | ALL |
| 644 | 24 | | PK | 6-0 | 27-81-31 | D02284 | | A1 | | | | | D05894J | 7 | | | ALL |
| 645 | 24 | | PK | 3-0 | 27-51-31 | D02268 | | A2 | | | | | TB0074Y | A008 | BJ | | ALL |
| 646 | 24 | | PK | 3-0 | 27-51-31 | D02268 | | X1 | | | | | TB0074Y | A008 | BJ | | ALL |
| 647 | 24 | | PK | 6-0 | 27-51-31 | D05894J | | 1 | | | | | TB0074Y | A008 | BJ | | ALL |
| 648 | 24 | | PK | 6-0 | 27-51-31 | D02268 | | X2 | | | | | D05300J | 12 | | | ALL |
| 649 | 24 | | PK | 6-0 | 27-51-31 | D02268 | | A1 | | | | | D05894J | 6 | | | ALL |
| 64A | 22 | | PA | 5-0 | 30-34-11 | D06582J | | 8 | | | | | TB0302X | B006 | BJ | | 050-099, 150-199 |
| 64A | 22 | | PA | 6-0 | 30-34-11 | D06582J | | 8 | | | | | TB0302X | B006 | BJ | | 275-299 |
| 64E | 20 | | UA | 7-0 | 21-66-31 | TB0318X | | | | | | | GDX0008 | S.. | 2 | | 050-099, 150, 152-157, 167-199 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 44

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-------------|-----------------|-------|---------------------------------------|----------|---------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | | 286T0176 | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 64E | 20 | PA | | 7-0 | 21-66-31 | TB0318X | | | | | FX | GDX0008 | S.. | 2 | | 162-166 |
| 64S | 24 | PK | | 9-0 | 78-36-11 | D05832J | | 47 | | | | D03528 | B2 | | | 050-099 |
| 64S | 24 | PK | | 10-0 | 78-36-11 | D05832J | | 47 | | | | D03528 | B2 | | | 150-199, 275-299 |
| 650 | 20 | PA | | 3-0 | 27-21-11 | D05300J | | 6 | | | | D05310J | 6 | | | ALL |
| 651 | 20 | PQ | | 4-0 | 27-23-11 | D05308J | | 21 | | | | D05310J | 7 | | | ALL |
| 651Z | | | BJ | 0-0 | 27-23-11 | D05308J | | DED | | | | D05310J | DED | | | ALL |
| 652 | 20 | PQ | BK | 4-0 | 27-23-11 | D05308J | | 23 | | | | D05310J | 4 | | | ALL |
| 652Z | | | BK | 0-0 | 27-23-11 | D05308J | | DED | | | | D05310J | DED | | | ALL |
| 653 | 22 | PQ | BL | 5-0 | 27-23-11 | D05308J | | 10 | | | | TB0302Y | C013 | BJ | | ALL |
| 653Z | | | BL | 0-0 | 27-23-11 | D05308J | | DED | | | | TB0302Y | DED | | | ALL |
| 654 | 24 | PK | | 6-0 | 34-12-12 | D03516 | | 11 | | | | D05433J | 16 | | | ALL |
| 655 | 24 | PK | | 6-0 | 34-12-12 | D03516 | | 10 | | | | D05433J | 17 | | | ALL |
| 657 | 20 | PA | | 3-0 | 21-58-11 | D03514 | | 7 | | | | GDX0015 | D.. | 2 | | ALL |
| 65A | 22 | PA | | 6-0 | 21-66-11 | D13848 | | X2 | | | | TB0318D | A004 | 2 | | 050-099 |
| 65A | 22 | PA | | 9-0 | 21-66-11 | D13848 | | X2 | | | | TB0318D | A004 | 2 | | 162-199 |
| 65E | 22 | PA | | 5-0 | 21-66-41 | D05060J | | 15 | | | | TB0318Z | 32 | BJ | | 050-099, 150, 152-199 |
| 65F | 24 | PK | | 6-0 | 36-21-11 | D05780J | | 25 | | | | TB0216Y | A018 | BJ | | 050-099, 162 |
| 65F | 24 | PK | | 5-0 | 36-21-11 | D05780J | | 25 | | | | TB0216Y | A018 | BJ | | 156-157, 166-199, 277-299 |
| 65H | 20 | PA | | 5-0 | 78-36-11 | D20090 | | A3 | | | | GDX0002 | D.. | 2 | | ALL |
| 65J | 24 | PK | | 10-0 | 78-36-11 | D20090 | | A1 | | | | D10164 | 6 | | | 050-099 |
| 65J | 24 | PK | | 12-0 | 78-36-11 | D20090 | | A1 | | | | D10164 | 6 | | | 150-199, 275-299 |
| 65K | 24 | PK | | 5-0 | 78-36-11 | D03492 | | A1 | | | | D03528 | B1 | | | ALL |
| 65L | 24 | PK | | 12-0 | 78-36-11 | D03492 | | A3 | | | | TB0250Y | A001 | BJ | | ALL |
| 65P | 24 | PK | | 6-0 | 78-36-11 | D05832J | | 48 | | | | D05306J | 29 | | | ALL |
| 65R | 24 | PK | | 12-0 | 78-36-11 | D05300J | | 57 | | | | D20090 | A2 | | | 050-099, 275-299 |
| 65R | 24 | PK | | 12-0 | 78-36-11 | D05300J | | 2 | | | | D20090 | A2 | | | 150-199 |
| 65W | 24 | PK | | 5-0 | 78-36-11 | D05306J | | 38 | | | | D04709J | 17 | | | ALL |
| 661 | 24 | PK | | 5-0 | 32-31-11 | D03512 | | B1 | | | | TB0220X | C004 | BJ | | 050-099, 275-299 |
| 661 | 24 | PK | | 4-0 | 32-31-11 | D03512 | | B1 | | | | TB0220X | C004 | BJ | | 150-199 |
| 662 | 20 | PA | | 6-0 | 32-31-11 | D03512 | | B2 | | | | GDX0004 | D.. | 2 | | ALL |
| 663 | 24 | PK | | 3-0 | 27-31-11 | D05312J | | 10 | | | | D05360J | 39 | | | 050-099, 275-299 |
| 663 | 24 | PK | | 5-0 | 27-31-11 | D05312J | | 10 | | | | D05360J | 39 | | | 150-199 |
| 664 | 20 | PA | | 7-0 | 33-42-21 | D01948 | | X2 | | | | K00435 | X2 | C | | ALL |
| 665 | 24 | PK | | 5-0 | 33-42-21 | D01948 | | X1 | | | | D04338J | 10 | | | ALL |
| 666 | 24 | PK | | 5-0 | 24-22-11 | D04802J | | 7 | | | | TB0220Y | A020 | BJ | | ALL |
| 667 | 24 | PK | | 7-0 | 32-09-11 | D02886 | | X1 | | | | TB0076Z | 8 | BJ | | ALL |
| 668 | 24 | PK | | 3-0 | 32-09-11 | D02886 | | X2 | | | | TB0074Z | 5 | BJ | | ALL |
| 66A | 22 | PA | | 2-0 | 21-66-11 | TB0318D | | A002 | 2 | | | TB0318D | A004 | 2 | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 45

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 670 | 20 | | PA | | 5-0 | 21-45-11 | D04338J | | 13 | | TB0222X | D002 | BJ | | ALL |
| 671 | 20 | | PA | | 6-0 | 21-45-11 | D01612 | | D2 | | D04338J | 14 | | | 050-099, 275-299 |
| 671 | 20 | | PA | | 7-0 | 21-45-11 | D01612 | | D2 | | D04338J | 14 | | | 150-199 |
| 672 | 24 | | PK | | 3-0 | 32-09-11 | D01612 | | X1 | | TB0074Z | 10 | BJ | | ALL |
| 673 | 24 | | PK | | 7-0 | 32-09-11 | D01612 | | X2 | | TB0076Z | 11 | BJ | | ALL |
| 674 | 24 | | PV | BR | 6-0 | 32-09-11 | D02910 | | X1 | | TB0216Z | 13 | BJ | | ALL |
| 674Z | | | | BR | 0-0 | 32-09-11 | D02910 | | DED | | TB0216Z | DED | | | ALL |
| 675 | 24 | | PV | BQ | 6-0 | 32-09-11 | D02910 | | X2 | | TB0076Y | A003 | BJ | | 050-099, 275-299 |
| 675 | 24 | | PV | BQ | 7-0 | 32-09-11 | D02910 | | X2 | | TB0076Y | A003 | BJ | | 150-199 |
| 675Z | | | | BQ | 0-0 | 32-09-11 | D02910 | | DED | | TB0076Y | DED | | | ALL |
| 676 | 24 | | PK | | 3-0 | 32-09-11 | D02912 | | 6 | | TB0074Z | 10 | BJ | | ALL |
| 677 | 24 | | PK | | 6-0 | 32-09-11 | D02912 | | 12 | | TB0076Z | 11 | BJ | | 050-099, 275-299 |
| 677 | 24 | | PK | | 7-0 | 32-09-11 | D02912 | | 12 | | TB0076Z | 11 | BJ | | 150-199 |
| 678 | 24 | | PK | | 6-0 | 32-09-11 | D02914 | | 6 | | TB0076Z | 8 | BJ | | 050-099, 275-299 |
| 678 | 24 | | PK | | 7-0 | 32-09-11 | D02914 | | 6 | | TB0076Z | 8 | BJ | | 150-199 |
| 67A | 22 | | PA | | 5-0 | 21-66-11 | D06934J | | 11 | | TB0318D | C005 | 2 | | 050-099, 162-199 |
| 67C | 20 | | PA | | 5-0 | 78-34-11 | D03536 | | C3 | | GDX0016 | D.. | 2 | | ALL |
| 67D | 20 | | PA | | 12-0 | 78-34-11 | D20102 | | X2 | | GDX0001 | D.. | 2 | | ALL |
| 67F | 24 | | PK | | 6-0 | 36-21-11 | D04904J | | 11 | | TB0216Y | A018 | BJ | | 050-099, 162 |
| 67F | 24 | | PK | | 5-0 | 36-21-11 | D04904J | | 11 | | TB0216Y | A018 | BJ | | 156-157, 166-199, 277-299 |
| 67G | 22 | | PQ | JU | 10-0 | 78-34-11 | D20102 | | X1 | | D04709J | 26 | | | ALL |
| 67GZ | | | | JU | 0-0 | 78-34-11 | D20102 | | DED | | D04709J | | | GU | ALL |
| 67H | 20 | | PQ | HI | 12-0 | 78-34-11 | D20102 | | A2 | | TB0318Z | 29 | BJ | | ALL |
| 67HZ | | | | HI | 0-0 | 78-34-11 | D20102 | | DED | | TB0318Z | | | HF | ALL |
| 67J | 24 | | PK | | 12-0 | 78-34-11 | D20102 | | B1 | | TB0318Z | 29 | BJ | | ALL |
| 67K | 20 | | PQ | HK | 12-0 | 78-34-11 | D20102 | | C2 | | TB0076Z | 10 | BJ | | ALL |
| 67KZ | | | | HK | 0-0 | 78-34-11 | D20102 | | DED | | TB0076Z | | | HJ | ALL |
| 680 | 22 | | PA | | 6-0 | 73-21-19 | D05300J | | 21 | | D02910 | D2 | | | 050-099 |
| 680 | 22 | | PA | | 5-0 | 73-21-19 | D05300J | | 21 | | D02910 | D2 | | | 150-199 |
| 680 | 22 | | PA | | 9-0 | 73-21-19 | D05300J | | 21 | | D02910 | D2 | | | 275-299 |
| 681 | 22 | | PA | | 5-0 | 73-21-19 | D05832J | | 13 | | D03622 | X1 | | | ALL |
| 682 | 22 | | PQ | YF | 5-0 | 73-21-19 | D05300J | | 22 | | D03622 | A2 | | | 050-099 |
| 682 | 22 | | PQ | DR | 5-0 | 73-21-19 | D05300J | | 22 | | D03622 | A2 | | | 150-199, 275-299 |
| 682Z | | | | YF | 0-0 | 73-21-19 | D05300J | | 20 | | D03622 | | | YE | 050-099 |
| 682Z | | | | DR | 0-0 | 73-21-19 | D05300J | | 20 | | D03622 | DED | | | 150-199 |
| 682Z | | | | DR | 0-0 | 73-21-19 | D05300J | | 20 | | D03622 | | | F6 | 275-299 |
| 683 | 22 | | PA | | 6-0 | 73-21-19 | TB0218Y | | C007 | BJ | D02910 | D1 | | | 050-099 |
| 683 | 22 | | PA | | 5-0 | 73-21-19 | TB0218Y | | C007 | BJ | D02910 | D1 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 46

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|-----|----|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | | | |
| 683 | 22 | | PA | | 9-0 | 73-21-19 | TB0218Y | C007 | | BJ | | | | D02910 | | D1 | | | 275-299 |
| 684 | 22 | | PA | | 9-0 | 73-21-19 | D05832J | | 15 | | | | | D12122 | | 14 | | | 050-099 |
| 684 | 22 | | PA | | 11-0 | 73-21-19 | D05832J | | 15 | | | | | D12122 | | 14 | | | 150-154 |
| 684 | 22 | | PA | | 10-0 | 73-21-19 | D05832J | | 15 | | | | | D12122 | | 14 | | | 155-199 |
| 684 | 22 | | PA | | 9-0 | 73-21-19 | D05832J | | 15 | | | | | TB0220X | A016 | | BJ | | 275-299 |
| 685 | 22 | | PQ | YE | 5-0 | 73-21-19 | D05300J | | 7 | | | | | D03622 | | A1 | | | 050-099 |
| 685 | 22 | | PQ | DQ | 5-0 | 73-21-19 | D05300J | | 7 | | | | | D03622 | | A1 | | | 150-199 |
| 685 | 22 | | PQ | DQ | 5-0 | 73-21-19 | D03622 | | A1 | | | | | D05300J | | 7 | | | 275-299 |
| 685Z | | | | YE | 0-0 | 73-21-19 | D05300J | | 5 | | | | | D03622 | | | | YE | 050-099 |
| 685Z | | | | DQ | 0-0 | 73-21-19 | D05300J | | 5 | | | | | D03622 | | DED | | | 150-199 |
| 685Z | | | | DQ | 0-0 | 73-21-19 | D03622 | | | | F6 | | | D05300J | | 5 | | | 275-299 |
| 686 | 20 | | PA | | 4-0 | 33-42-21 | D04932J | | 12 | | | | | D04338J | | 3 | | | 050-099 |
| 686 | 18 | | PA | | 4-0 | 33-42-21 | D04932J | | 12 | DL | | | | D04338J | | 3 | DK | | 150-199, 275-278 |
| 686 | 18 | | PA | | 4-0 | 33-42-21 | D04932J | | 12 | DK | | | | D04338J | | 3 | DK | | 280-299 |
| 689 | 20 | | PA | | 3-0 | 73-21-17 | D03474 | | B3 | | | | | GD0005 | | D.. | 2 | | ALL |
| 68A | 22 | | PA | | 5-0 | 21-66-11 | D06934J | | 12 | | | | | TB0318D | A002 | 2 | | | 050-099, 162-199 |
| 690 | 24 | | PK | | 6-0 | 73-21-17 | D05832J | | 12 | | | | | D03474 | | B2 | | | ALL |
| 692 | 24 | | PK | | 6-0 | 73-21-17 | D05832J | | 11 | | | | | TB0216Y | C001 | | BJ | | 050-099 |
| 692 | 24 | | PK | | 5-0 | 73-21-17 | D05832J | | 11 | | | | | TB0216Y | C001 | | BJ | | 150-199, 275-299 |
| 693 | 22 | | PA | | 9-0 | 78-34-11 | D05306J | | 19 | | | | | D20102 | | B2 | | | 050-099 |
| 693 | 22 | | PA | | 12-0 | 78-34-11 | D05306J | | 19 | | | | | D20102 | | B2 | | | 150-199, 275-299 |
| 695 | 24 | | PK | | 4-0 | 28-42-31 | D04662J | | 7 | | | | | D04932J | | 28 | | | ALL |
| 697 | 20 | | PQ | AH | 6-0 | 28-22-12 | K00329 | | X2 | C | | | | TB0216Y | C010 | | BJ | | ALL |
| 697Z | | | | AH | 0-0 | 28-22-12 | K00329 | | DED | | | | | TB0216Y | | DED | | | ALL |
| 698 | 24 | | PK | | 7-0 | 21-26-11 | TB0260Z | | 2 | BJ | | | | D05658J | | 1 | | | 050-099 |
| 698 | 24 | | PK | | 5-0 | 21-26-11 | TB0252Y | C001 | | BJ | | | | D05658J | | 1 | | | 150-154, 275 |
| 698 | 24 | | PK | | 6-0 | 21-26-11 | TB0260Z | | 2 | BJ | | | | D05658J | | 1 | | | 155-199, 276-299 |
| 699 | 24 | | PK | | 5-0 | 21-26-11 | K00347 | | X2 | C | | | | D05658J | | 3 | | | ALL |
| 69A | 22 | | PA | | 5-0 | 21-66-11 | TB0318D | C002 | | 2 | | | | D04802J | | 5 | | | 050-099, 162-199 |
| 6A1 | 24 | | PK | | 3-0 | 27-89-11 | D05894J | | 12 | | | | | D05832J | | 52 | | | 050-099, 150-157, 275-299 |
| 6A1 | 24 | | PK | | 3-0 | 27-89-11 | D05894J | | 2 | | | | | D05832J | | 52 | | | 162-199 |
| 701 | 24 | | PK | | 3-0 | 36-11-61 | D05780J | | 33 | | | | | D04662J | | 13 | | | ALL |
| 702 | 24 | | PK | | 3-0 | 36-11-61 | D05780J | | 34 | | | | | D04662J | | 14 | | | ALL |
| 704 | 20 | | PA | | 3-0 | 21-26-11 | SP01622 | | | | W | | | GD0008 | | D.. | 2 | | ALL |
| 705 | 24 | | PK | | 6-0 | 21-26-11 | SP01620 | | | | W | | | D05658J | | 5 | | | ALL |
| 706 | 24 | | PK | | 5-0 | 21-26-11 | D05658J | | 6 | | | | | TB0302X | B001 | | BJ | | ALL |
| 707 | 24 | | PK | | 6-0 | 32-42-11 | D01172 | | X2 | | | | | D05433J | | 10 | | | ALL |
| 708 | 24 | | PK | | 5-0 | 32-42-11 | D01172 | | X1 | | | | | D04906J | | 9 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 47

Aug 05/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 709 | 24 | | PK | 6-0 | 34-53-11 | D03554 | | 11 | | | | | D05433J | 22 | | | ALL |
| 70J | 20 | | PA | 7-0 | 38-32-11 | TB0222X | | C010 | BJ | | | | D05433J | 39 | | | 050-099, 155-199, 277-299 |
| 70J | 20 | | PA | 7-0 | SPARE | TB0222X | | C010 | BJ | | | | D05433J | 39 | | | 276 |
| 70K | 22 | | PA | 5-0 | 32-45-11 | D05832J | | 25 | | | | | TB0302Y | C024 | BJ | | 050-099, 150-199 |
| 70K | 22 | | PA | 6-0 | 32-45-11 | D05832J | | 25 | | | | | D06286J | 4 | | | 275-299 |
| 70M | 24 | | PK | 10-0 | 21-58-11 | D04662J | | 27 | | | | | TB0080D | A012 | 2 | | 050-099 |
| 70M | 24 | | PK | 8-0 | 21-58-11 | D04662J | | 27 | | | | | TB0080D | A012 | 2 | | 150-199, 275-299 |
| 710 | 20 | | PA | 3-0 | 34-53-11 | D03554 | | 10 | | | | | GDX0005 | D.. | 2 | | ALL |
| 711 | 24 | | PK | 6-0 | 27-32-11 | D02914 | | 13 | | | | | D05433J | 35 | | | ALL |
| 712 | 20 | | PA | 3-0 | 27-32-11 | D02914 | | 1 | | | | | GDX0006 | D.. | 2 | | ALL |
| 713 | 20 | | UA | 6-0 | 32-42-11 | D01172 | | | | | | | GDX0004 | S.. | 2 | | 050-099, 275-299 |
| 713 | 20 | | UA | 8-0 | 32-42-11 | D01172 | | | | | | | GDX0004 | S.. | 2 | | 150-199 |
| 716 | 18 | | PA | 6-0 | 28-22-11 | K00190 | | X1 | C | | | | D04662J | 3 | DK | | 050-099, 275-299 |
| 716 | 18 | | PA | 5-0 | 28-22-11 | K00190 | | X1 | C | | | | D04662J | 3 | DK | | 150-199 |
| 717 | 20 | | PA | 3-0 | 28-22-11 | K00190 | | X2 | C | | | | GDX0017 | D.. | 2 | | 050-099 |
| 717 | 20 | | PA | 2-0 | 28-22-11 | K00190 | | X2 | C | | | | GDX0017 | D.. | 2 | | 150-199 |
| 717 | 20 | | PA | 4-0 | 28-22-11 | K00190 | | X2 | C | | | | GDX0017 | D.. | 2 | | 275-299 |
| 718 | 22 | | PQ | DB | 12-0 | 74-31-11 | D05306J | 20 | | | | | D10160 | B1 | | * | 050-099 |
| 718 | 22 | | PQ | DB | 4-0 | 74-31-11 | D05306J | 20 | | | | | D10160 | B1 | | * | 150-199, 275-299 |
| 718Z | | | | DB | 0-0 | 74-31-11 | D05306J | DED | | | | | D10160 | DED | | | ALL |
| 719 | 22 | | PQ | DM | 4-0 | 74-31-11 | D05306J | 7 | | | | | TB0222X | C002 | BJ | | ALL |
| 719Z | | | | DM | 0-0 | 74-31-11 | D05306J | DED | | | | | TB0222X | DED | | | ALL |
| 71A | 22 | | PA | 5-0 | 36-11-51 | D05658J | | 10 | | | | | TB0252Z | 11 | BJ | | 050-099, 275-276 |
| 71A | 22 | | PA | 6-0 | 36-11-51 | D05658J | | 10 | | | | | TB0252Z | 11 | BJ | | 150-156, 162-166 |
| 71B | 22 | | PA | 3-0 | 36-11-51 | TB0252Z | | 11 | BJ | | | | D11882 | 6 | | | 050-099, 275-276 |
| 71B | 22 | | PA | 3-0 | 36-11-51 | D11882 | | 6 | | | | | TB0252Z | 11 | BJ | | 150-155, 162-165 |
| 71B | 22 | | PA | 4-0 | 36-11-51 | D11882 | | 6 | | | | | TB0252Z | 11 | BJ | | 156, 166 |
| 71C | 22 | | PA | 3-0 | 36-11-51 | TB0252Z | | 11 | BJ | | | | D11882 | 3 | | | 050-099, 275-276 |
| 71C | 22 | | PA | 3-0 | 36-11-51 | D11882 | | 3 | | | | | TB0252Z | 11 | BJ | | 150-155, 162-165 |
| 71C | 22 | | PA | 4-0 | 36-11-51 | D11882 | | 3 | | | | | TB0252Z | 11 | BJ | | 156, 166 |
| 71D | 22 | | PA | 3-0 | 36-11-51 | TB0252Y | | A009 | BJ | | | | D11882 | 1 | | | 050-099, 275-276 |
| 71D | 22 | | PA | 3-0 | 36-11-51 | D11882 | | 1 | | | | | TB0252Y | A009 | BJ | | 150-155, 162-165 |
| 71D | 22 | | PA | 4-0 | 36-11-51 | D11882 | | 1 | | | | | TB0252Y | A009 | BJ | | 156, 166 |
| 71E | 20 | | PA | 5-0 | 36-11-51 | D05658J | | 11 | | | | | TB0252Y | A009 | BJ | | 050-099, 150-199 |
| 71E | 20 | | PA | 5-0 | 36-11-51 | TB0252Y | | A009 | BJ | | | | D05658J | 11 | | | 275-299 |
| 71F | 22 | | PA | 3-0 | 36-11-51 | TB0252Z | | 11 | BJ | | | | D11884 | 6 | | | 050-099, 275-276 |
| 71F | 22 | | PA | 3-0 | 36-11-51 | D11884 | | 6 | | | | | TB0252Z | 11 | BJ | | 150-155, 162-165 |
| 71F | 22 | | PA | 4-0 | 36-11-51 | D11884 | | 6 | | | | | TB0252Z | 11 | BJ | | 156, 166 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 48

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 71G | 22 | | PA | | 3-0 | 36-11-51 | TB0252Z | 11 | BJ | | D11884 | | 3 | | 050-099, 150-155, 162-165, 275-276 |
| 71G | 22 | | PA | | 4-0 | 36-11-51 | TB0252Z | 11 | BJ | | D11884 | | 3 | | 156, 166 |
| 71H | 20 | | PA | | 5-0 | 36-11-51 | D05658J | 12 | | | TB0252Y | C009 | BJ | | 050-099, 150-199 |
| 71H | 20 | | PA | | 5-0 | 36-11-51 | TB0252Y | | C009 | BJ | D05658J | | 12 | | 275-299 |
| 71J | 22 | | PA | | 3-0 | 36-11-51 | TB0252Y | | C009 | BJ | D11884 | | 1 | | 050-099, 275-276 |
| 71J | 22 | | PA | | 3-0 | 36-11-51 | D11884 | 1 | | | TB0252Y | C009 | BJ | | 150-155, 162-165 |
| 71J | 22 | | PA | | 4-0 | 36-11-51 | D11884 | 1 | | | TB0252Y | C009 | BJ | | 156, 166 |
| 71K | 20 | | PA | | 5-0 | 36-11-51 | TB0252Y | | C009 | BJ | D04932J | | 56 | | 050-099, 275-299 |
| 71K | 20 | | PA | | 5-0 | 36-11-51 | D04932J | 56 | | | TB0252Y | C009 | BJ | | 150-199 |
| 71L | 20 | | PA | | 5-0 | 36-11-51 | TB0252Y | | A009 | BJ | D04932J | | 54 | | 050-099, 275-299 |
| 71L | 20 | | PA | | 5-0 | 36-11-51 | D04932J | 54 | | | TB0252Y | A009 | BJ | | 150-199 |
| 71M | 22 | | PA | | 8-0 | 36-11-61 | TB0252Z | 11 | BJ | | TB0260Z | | 3 | BJ | 050-099 |
| 71M | 22 | | PA | | 5-0 | 36-11-61 | TB0252Z | 11 | BJ | | TB0260Z | | 3 | BJ | 150-154 |
| 71M | 22 | | PA | | 6-0 | 36-11-61 | TB0252Z | 11 | BJ | | TB0260Z | | 3 | BJ | 155-156, 162-166, 276 |
| 71M | 22 | | PA | | 5-0 | 36-11-61 | TB0260Z | 3 | BJ | | TB0252Z | | 11 | BJ | 275 |
| 71N | 22 | | PA | | 10-0 | 36-11-61 | TB0260Z | 3 | BJ | | D11886 | | 6 | | 050-099 |
| 71N | 22 | | PA | | 3-0 | 36-11-61 | D11886 | 6 | | | TB0260Z | | 3 | BJ | 150-154 |
| 71N | 22 | | PA | | 6-0 | 36-11-61 | TB0260Z | 3 | BJ | | D11886 | | 6 | | 155-156, 162-166, 276 |
| 71N | 22 | | PA | | 3-0 | 36-11-61 | TB0260Z | 3 | BJ | | D11886 | | 6 | | 275 |
| 71P | 22 | | PA | | 3-0 | 36-11-61 | TB0252Z | 11 | BJ | | D11886 | | 3 | | 050-099, 275-276 |
| 71P | 22 | | PA | | 3-0 | 36-11-61 | D11886 | 3 | | | TB0252Z | | 11 | BJ | 150-155, 162-165 |
| 71P | 22 | | PA | | 4-0 | 36-11-61 | D11886 | 3 | | | TB0252Z | | 11 | BJ | 156, 166 |
| 71R | 22 | | PA | | 3-0 | 36-11-61 | D11886 | 1 | | | TB0252Y | A010 | BJ | | 050-099, 150-155, 162-165 |
| 71R | 22 | | PA | | 4-0 | 36-11-61 | D11886 | 1 | | | TB0252Y | A010 | BJ | | 156, 166 |
| 71R | 22 | | PA | | 3-0 | 36-11-61 | TB0252Y | A010 | BJ | | D11886 | | 1 | | 275-276 |
| 71S | 22 | | PA | | 5-0 | 36-11-61 | D05780J | 5 | | | TB0252Y | A010 | BJ | | 050-099 |
| 71S | 20 | | PA | | 5-0 | 36-11-61 | D05780J | 5 | | | TB0252Y | A010 | BJ | | 150-199 |
| 71S | 22 | | PA | | 5-0 | 36-11-61 | TB0252Y | A010 | BJ | | D05780J | | 5 | | 275-299 |
| 71T | 22 | | PA | | 5-0 | 36-11-61 | D04662J | 54 | | | TB0252Y | A010 | BJ | | 050-099 |
| 71T | 22 | | PA | | 6-0 | 36-11-61 | TB0252Y | A010 | BJ | | D04662J | | 54 | | 150-199 |
| 71T | 22 | | PA | | 5-0 | 36-11-61 | TB0252Y | A010 | BJ | | D04662J | | 54 | | 275-299 |
| 71U | 22 | | PA | | 5-0 | 36-11-61 | D05780J | 3 | | | TB0252Y | C010 | BJ | | 050-099, 150-199 |
| 71U | 22 | | PA | | 5-0 | 36-11-61 | TB0252Y | C010 | BJ | | D05780J | | 3 | | 275-299 |
| 71V | 22 | | PA | | 5-0 | 36-11-61 | D04662J | 53 | | | TB0252Y | C010 | BJ | | 050-099 |
| 71V | 22 | | PA | | 10-0 | 36-11-61 | TB0252Y | C010 | BJ | | D04662J | | 53 | | 150-199 |
| 71V | 22 | | PA | | 5-0 | 36-11-61 | TB0252Y | C010 | BJ | | D04662J | | 53 | | 275-299 |
| 71W | 22 | | PA | | 10-0 | 36-11-61 | TB0260Z | 3 | BJ | | D11888 | | 6 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0170
Page 49
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 71W | 22 | | PA | 7-0 | 36-11-61 | D11888 | | 6 | | | | | TB0260Z | 3 | BJ | | 150-154 |
| 71W | 22 | | PA | 6-0 | 36-11-61 | TB0260Z | | 3 | BJ | | | | D11888 | 6 | | | 155-156, 162-166, 276 |
| 71W | 22 | | PA | 7-0 | 36-11-61 | TB0260Z | | 3 | BJ | | | | D11888 | 6 | | | 275 |
| 71X | 22 | | PA | 10-0 | 36-11-61 | TB0260Z | | 3 | BJ | | | | D11888 | 3 | | | 050-099 |
| 71X | 22 | | PA | 7-0 | 36-11-61 | D11888 | | 3 | | | | | TB0260Z | 3 | BJ | | 150-154 |
| 71X | 22 | | PA | 6-0 | 36-11-61 | TB0260Z | | 3 | BJ | | | | D11888 | 3 | | | 155-156, 162-166, 276 |
| 71X | 22 | | PA | 7-0 | 36-11-61 | TB0260Z | | 3 | BJ | | | | D11888 | 3 | | | 275 |
| 71Y | 22 | | PA | 3-0 | 36-11-61 | D11892 | | 6 | | | | | TB0252Z | 12 | BJ | | 050-099, 150-155, 162-165 |
| 71Y | 22 | | PA | 4-0 | 36-11-61 | D11892 | | 6 | | | | | TB0252Z | 12 | BJ | | 156, 166 |
| 71Y | 22 | | PA | 3-0 | 36-11-61 | TB0252Z | | 12 | BJ | | | | D11892 | 6 | | | 275-276 |
| 721 | 18 | | PA | 5-0 | 28-22-11 | K00187 | | X1 | C | | | | D04662J | 4 | DK | | ALL |
| 722 | 20 | | PA | 3-0 | 28-22-11 | K00187 | | X2 | C | | | | GDX0017 | D.. | 2 | | 050-099, 275-299 |
| 722 | 20 | | PA | 2-0 | 28-22-11 | K00187 | | X2 | C | | | | GDX0017 | D.. | 2 | | 150-199 |
| 725 | 20 | | PA | 5-0 | 33-42-21 | D04672J | | 22 | | | | | D01948 | B2 | | | 050-099 |
| 725 | 18 | | PA | 6-0 | 33-42-21 | D04672J | | 22 | FL | | | | D01948 | B2 | | | 150-199 |
| 725 | 18 | | PA | 6-0 | 33-42-21 | D04672J | | 22 | DL | | | | D01948 | B2 | | | 275-299 |
| 728 | 20 | | PA | 5-0 | 33-42-21 | D04672J | | 42 | | | | | D01948 | A2 | | | 050-099 |
| 728 | 18 | | PA | 6-0 | 33-42-21 | D04672J | | 42 | DL | | | | D01948 | A2 | | | 150-199, 275-299 |
| 72A | 22 | | PA | 3-0 | 36-11-61 | D11890 | | 3 | | | | | TB0252Z | 12 | BJ | | 050-099, 150-155, 162-165 |
| 72A | 22 | | PA | 4-0 | 36-11-61 | D11890 | | 3 | | | | | TB0252Z | 12 | BJ | | 156, 166 |
| 72A | 22 | | PA | 3-0 | 36-11-61 | TB0252Z | | 12 | BJ | | | | D11890 | 3 | | | 275-276 |
| 72B | 22 | | PA | 3-0 | 36-11-61 | D11890 | | 6 | | | | | TB0252Z | 12 | BJ | | 050-099, 150-155, 162-165 |
| 72B | 22 | | PA | 4-0 | 36-11-61 | D11890 | | 6 | | | | | TB0252Z | 12 | BJ | | 156, 166 |
| 72B | 22 | | PA | 3-0 | 36-11-61 | TB0252Z | | 12 | BJ | | | | D11890 | 6 | | | 275-276 |
| 72C | 22 | | PA | 3-0 | 36-11-61 | D11888 | | 1 | | | | | TB0252Y | C010 | BJ | | 050-099 |
| 72C | 22 | | PA | 3-0 | 36-11-61 | TB0252Y | | C010 | BJ | | | | D11888 | 1 | | | 150-155, 162-165, 275-276 |
| 72C | 22 | | PA | 4-0 | 36-11-61 | TB0252Y | | C010 | BJ | | | | D11888 | 1 | | | 156, 166 |
| 72D | 22 | | PA | 5-0 | 36-11-61 | D11892 | | 1 | | | | | TB0218Y | C013 | BJ | | 050-099, 156, 166, 275-276 |
| 72D | 22 | | PA | 4-0 | 36-11-61 | D11892 | | 1 | | | | | TB0218Y | C013 | BJ | | 150-155, 162-165 |
| 72E | 22 | | PA | 5-0 | 36-11-61 | D11890 | | 1 | | | | | TB0220Y | A002 | BJ | | 050-099, 156, 166, 275-276 |
| 72E | 22 | | PA | 4-0 | 36-11-61 | D11890 | | 1 | | | | | TB0220Y | A002 | BJ | | 150-155, 162-165 |
| 72F | 22 | | PA | 3-0 | 36-11-61 | D11892 | | 3 | | | | | TB0252Z | 12 | BJ | | 050-099, 150-155, 162-165 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 50

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 72F | 22 | | PA | 4-0 | 36-11-61 | D11892 | | 3 | | | | | TB0252Z | 12 | BJ | | 156, 166 |
| 72F | 22 | | PA | 3-0 | 36-11-61 | TB0252Z | | 12 | BJ | | | | D11892 | 3 | | | 275-276 |
| 72J | 24 | | PK | 6-0 | 21-58-16 | D12244 | | 1 | | | | | TB0272Z | 16 | BJ | | 050-099, 155-199, 276-299 |
| 72N | 20 | | PA | 9-0 | 36-11-61 | D04662J | | 36 | | | | | TB0252Z | 12 | BJ | | 050-099 |
| 72N | 20 | | PA | 6-0 | 36-11-61 | D04662J | | 55 | | | | | TB0252Z | 12 | BJ | | 150-154 |
| 72N | 20 | | PA | 6-0 | 36-11-61 | D04662J | | 36 | | | | | TB0252Z | 12 | BJ | | 155-156, 162-166, 275-276 |
| 72P | 22 | | PA | 15-0 | 21-45-22 | C00678 | | | CAP | Y | | | D13804 | A2 | | | 050-099, 155-199, 276-299 |
| 72P | 22 | | PA | 8-0 | 21-45-22 | C00678 | | | CAP | Y | | | D13804 | A2 | | | 150-154, 275 |
| 72R | 20 | | PA | 8-0 | 21-45-22 | D11798 | | 8 | | | | | GDX0005 | D.. | 2 | | 050-099, 150-199, 275 |
| 72R | 20 | | PA | 13-0 | 21-45-22 | D11798 | | 8 | | | | | GDX0005 | D.. | 2 | | 276-299 |
| 737 | 18 | | PA | 6-0 | 33-42-21 | D01948 | | | B1 | | | | D05714J | 3 | | | ALL |
| 73H | 24 | | PK | 8-0 | 21-45-22 | D04662J | | 38 | | | | | D13804 | X1 | | | ALL |
| 73J | 24 | | PK | 10-0 | 21-45-22 | D13804 | | | X2 | | | | D11798 | 7 | | | 050-099, 155-199, 276-299 |
| 73J | 24 | | PK | 8-0 | 21-45-22 | D13804 | | | X2 | | | | D11798 | 7 | | | 150-154, 275 |
| 73K | 22 | | PA | 7-0 | 34-45-13 | D02914 | | 7 | | | | | D05431J | 17 | | | 050-099, 277-299 |
| 73K | 22 | | PA | 6-0 | 34-45-13 | D02914 | | 7 | | | | | D05431J | 17 | | | 150-152, 155-199 |
| 73K | 22 | | PA | 6-0 | 34-45-13 | D02914 | | 7 | | | | | D05431J | 23 | | | 153-154 |
| 73P | 22 | | PA | 11-0 | 21-45-22 | D13804 | | | A1 | | | | TB0076X | A002 | BJ | | 050-099, 155-199, 276-299 |
| 73P | 22 | | PA | 8-0 | 21-45-22 | D13804 | | | A1 | | | | TB0076X | A002 | BJ | | 150-154, 275 |
| 74K | 20 | | PA | 13-0 | 76-11-11 | D11752 | | | B2 | | | | GDX0001 | D.. | 2 | | ALL |
| 74L | 20 | | PA | 6-0 | 34-45-13 | D02914 | | | 8 | | | | GDX0003 | D.. | 2 | | 050-099, 150-199, 277-299 |
| 74M | 22 | | PA | 6-0 | 28-31-21 | D12156 | | | X1 | | | | TB0074Y | A012 | BJ | | 050-099, 155-199, 276-299 |
| 74N | 20 | | PA | 6-0 | 28-31-21 | D12156 | | | X2 | | | | GDX0005 | D.. | 2 | | 050-099, 155-199, 276-299 |
| 74R | 20 | | PA | 7-0 | 21-58-16 | D12244 | | | 2 | | | | GDX0009 | D.. | 2 | | 050-099, 155-199, 276-299 |
| 74T | 22 | | PA | 7-0 | 28-31-21 | K02093 | | | X1 | C | | | TB0074Y | A012 | BJ | | 050-099 |
| 74T | 22 | | PA | 6-0 | 28-31-21 | K02093 | | | X1 | C | | | TB0074Y | A012 | BJ | | 162-164, 276 |
| 74U | 20 | | PA | 3-0 | 28-31-21 | K02093 | | | X2 | C | | | GDX0008 | D.. | 2 | | 050-099 |
| 74U | 20 | | PA | 4-0 | 28-31-21 | K02093 | | | X2 | C | | | GDX0008 | D.. | 2 | | 162-164, 276 |
| 74W | 22 | | PA | 6-0 | 28-31-21 | D04662J | | | 28 | | | | TB0074Y | A012 | BJ | | 050-099, 155-199, 276-299 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 51

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 74X | 22 | | PA | | 2-0 | 28-31-21 | TB0074Y | A012 | BJ | | TB0074D | A015 | 2 | | 050-099, 162-164, 276 |
| 74X | 22 | | PA | | 9-0 | 28-31-21 | TB0074Y | A012 | BJ | | K02091 | X1 | C | | 155-157, 165-199, 277-299 |
| 752 | 22 | | PQ | EG | 5-0 | 27-09-12 | TB0220X | B005 | BJ | | D02912 | | 13 | | 050-099, 275-299 |
| 752 | 22 | | PQ | EG | 6-0 | 27-09-12 | TB0220X | B005 | BJ | | D02912 | | 13 | | 150-199 |
| 752Z | | | | EG | 0-0 | 27-09-12 | TB0220X | DED | | | D02912 | DED | | | ALL |
| 759 | 18 | | PQ | CV | 6-0 | 28-41-12 | TB0220F | C018 | 2 | | D00340 | A3 | | | 050-099, 275-299 |
| 759 | 18 | | PQ | CV | 5-0 | 28-41-12 | TB0220F | C018 | 2 | | D00340 | A3 | | | 150-199 |
| 759Z | | | | CV | 0-0 | 28-41-12 | TB0220F | DED | | | D00340 | DED | | | ALL |
| 75A | 20 | | PQ | DW | 11-0 | 28-31-12 | D12164 | | 2 | | GD00012 | D.. | 2 | | 050-099 |
| 75A | 20 | | PQ | FT | 11-0 | 28-31-12 | D12164 | | 2 | | GD00012 | D.. | 2 | | 155-199, 276-299 |
| 75AZ | | | | DW | 0-0 | 28-31-12 | D12164 | DED | | | GD00012 | DED | | | 050-099 |
| 75AZ | | | | FT | 0-0 | 28-31-12 | D12164 | DED | | | GD00012 | DED | | | 155-199, 276-299 |
| 75B | 22 | | PA | | 7-0 | 28-31-12 | D05780J | | 40 | | D12164 | | 3 | | 050-099 |
| 75B | 22 | | PA | | 6-0 | 28-31-12 | D05780J | | 40 | | D12164 | | 3 | | 155-199, 276-299 |
| 75C | 22 | | PQ | DV | 9-0 | 28-31-12 | D12164 | | 4 | | TB0302D | C037 | 2 | | 050-099 |
| 75C | 22 | | PQ | FU | 8-0 | 28-31-12 | D12164 | | 4 | | TB0302D | C037 | 2 | | 155-199, 276-299 |
| 75CZ | | | | DV | 0-0 | 28-31-12 | D12164 | DED | | | TB0302D | DED | | | 050-099 |
| 75CZ | | | | FU | 0-0 | 28-31-12 | D12164 | DED | | | TB0302D | DED | | | 155-199, 276-299 |
| 75D | 20 | | PA | | 11-0 | 28-31-12 | D12164 | | 7 | | GD00012 | D.. | 2 | | 050-099, 155-199, 276-299 |
| 75E | 22 | | PQ | DU | 5-0 | 28-31-12 | D05894J | | 4 | | TB0302D | C037 | 2 | | 050-099 |
| 75E | 22 | | PQ | FV | 5-0 | 28-31-12 | D05894J | | 4 | | TB0302D | C037 | 2 | | 155-199, 276-299 |
| 75EZ | | | | DU | 0-0 | 28-31-12 | D05894J | DED | | | TB0302D | DED | | | 050-099 |
| 75EZ | | | | FV | 0-0 | 28-31-12 | D05894J | DED | | | TB0302D | DED | | | 155-199, 276-299 |
| 75F | 20 | | PA | | 4-0 | 28-31-12 | D05780J | | 38 | | D05894J | | 9 | | 050-099 |
| 75F | 20 | | PA | | 3-0 | 28-31-12 | D05780J | | 38 | | D05894J | | 9 | | 155-199, 276-299 |
| 75G | 20 | | PA | | 4-0 | 28-31-12 | D05780J | | 39 | | D05894J | | 10 | | 050-099 |
| 75G | 20 | | PA | | 3-0 | 28-31-12 | D05780J | | 39 | | D05894J | | 10 | | 155-199, 276-299 |
| 75H | 22 | | PQ | DR | 7-0 | 28-31-11 | D12160 | | A2 | | D05658J | | 53 | | 050-099 |
| 75H | 22 | | PQ | FW | 6-0 | 28-31-11 | D05658J | | 53 | | D12160 | A2 | | | 155-199, 276-299 |
| 75HZ | | | | DR | 0-0 | 28-31-11 | D12160 | DED | | | D05658J | DED | | | 050-099 |
| 75HZ | | | | FW | 0-0 | 28-31-11 | D05658J | DED | | | D12160 | DED | | | 155-199, 276-299 |
| 75J | 20 | | PQ | DQ | 8-0 | 28-31-11 | D12160 | | A3 | | GD00007 | D.. | 2 | | 050-099 |
| 75J | 20 | | PQ | FX | 7-0 | 28-31-11 | D12160 | | A3 | | GD00007 | D.. | 2 | | 155-157, 276-299 |
| 75J | 20 | | PQ | FX | 8-0 | 28-31-11 | D12160 | | A3 | | GD00007 | D.. | 2 | | 162-199 |
| 75JZ | | | | DQ | 0-0 | 28-31-11 | D12160 | DED | | | GD00007 | DED | | | 050-099 |
| 75JZ | | | | FX | 0-0 | 28-31-11 | D12160 | DED | | | GD00007 | DED | | | 155-199, 276-299 |
| 75K | 22 | | PA | | 7-0 | 28-31-11 | D05780J | | 37 | | D12160 | C1 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 52

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|---------|--------|-------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 75K | 22 | | PA | | 6-0 | 28-31-11 | D05780J | | | | | | | | 155-199, 276-299 |
| 75L | 22 | | PA | | 7-0 | 28-31-11 | D12160 | | X1 | | | | | | 050-099 |
| 75L | 22 | | PA | | 6-0 | 28-31-11 | D05658J | | | 50 | | | X1 | | 155-199, 276-299 |
| 75M | 20 | | PA | | 8-0 | 28-31-11 | D12160 | | X2 | | GDX0007 | | D.. | 2 | 050-099, 162-199 |
| 75M | 20 | | PA | | 7-0 | 28-31-11 | D12160 | | X2 | | GDX0007 | | D.. | 2 | 155-157, 276-299 |
| 75N | 20 | | PA | | 4-0 | 28-31-11 | D05780J | | | 35 | | | 52 | | 050-099 |
| 75N | 20 | | PA | | 3-0 | 28-31-11 | D05780J | | | 35 | | | 52 | | 155-199, 276-299 |
| 75R | 24 | | PK | | 7-0 | 21-58-12 | D12244 | | | 9 | | | C005 | 2 | 050-099, 155-199, 276-299 |
| 75S | 24 | | PK | | 8-0 | 21-58-12 | D12244 | | | 6 | | | | 2 | BJ 050-099, 155-199, 276-299 |
| 75T | 20 | | PA | | 4-0 | 28-31-11 | D05780J | | | 36 | | | 51 | | 050-099 |
| 75T | 20 | | PA | | 3-0 | 28-31-11 | D05780J | | | 36 | | | 51 | | 155-199, 276-299 |
| 75U | 24 | | PK | | 6-0 | 21-58-12 | D12244 | | | 12 | | | K02091 | | 050-099, 155-199, 276-299 |
| 75W | 22 | | PA | | 20-0 | 28-22-12 | TB0216Z | | | 19 | BJ | | K00329 | X1 | C 050-099 |
| 75W | 22 | | PA | | 20-0 | 28-22-12 | K00329 | | X1 | | C | | TB0216Z | 19 | BJ 150-157, 275-278 |
| 75W | 22 | | PA | | 20-0 | 28-22-12 | K00329 | | X1 | | C | | TB0216Z | 14 | BJ 162-199, 280-299 |
| 767 | 22 | | PQ | CZ | 8-0 | 28-41-21 | D04904J | | | 15 | | | TB0272G | 9 | 2 050-099, 275-299 |
| 767 | 22 | | PQ | CZ | 5-0 | 28-41-21 | D04904J | | | 15 | | | TB0272G | 9 | 2 150-199 |
| 767Z | | | | CZ | 0-0 | 28-41-21 | D04904J | | | | DED | | TB0272G | | DED ALL |
| 768 | 22 | | PQ | DF | 5-0 | 28-42-11 | D04662J | | | 5 | | | TB0302Y | A012 | BJ ALL |
| 768Z | | | | DF | 0-0 | 28-42-11 | D04662J | | | | DED | | TB0302Y | | DED ALL |
| 76D | 20 | | PA | | 3-0 | 21-58-12 | K02091 | | | 11 | C | | GDX0009 | D.. | 2 050-099, 155-199, 276-299 |
| 76P | 20 | | PQ | GS | 5-0 | 28-31-12 | D05894J | | | 17 | | | D02910 | | C2 050-099, 155-199, 277-299 |
| 76PZ | | | | GS | 0-0 | 28-31-12 | D05894J | | | | DED | | D02910 | | DED 050-099, 155-199, 277-299 |
| 76Q | 20 | | PQ | GT | 6-0 | 28-31-12 | TB0302D | | | | A037 | 2 | D02910 | | C3 050-099 |
| 76Q | 20 | | PQ | GT | 6-8 | 28-31-12 | TB0302D | | | | A037 | 2 | D02910 | | C3 155-199, 277-299 |
| 76QZ | | | | GT | 0-0 | 28-31-12 | TB0302D | | | | DED | | D02910 | | DED 050-099, 155-199, 277-299 |
| 771 | 24 | | PK | | 5-0 | 21-25-11 | D04672J | | | 38 | | | TB0302F | A009 | 2 050-099, 275-299 |
| 771 | 24 | | PK | | 4-0 | 21-25-11 | D04672J | | | 38 | | | TB0302F | A009 | 2 150-199 |
| 772 | 24 | | PK | | 5-0 | 36-23-11 | D04672J | | | 8 | | | TB0222X | C009 | BJ ALL |
| 773 | 12 | | PA | | 7-0 | 21-58-14 | D06286J | | | 1 | | | K00343 | A1 | E 050-099, 275-299 |
| 773 | 12 | | PA | | 6-0 | 21-58-14 | D06286J | | | 1 | | | K00343 | A1 | E 150-199 |
| 774 | 12 | | PA | | 7-0 | 21-58-14 | D06286J | | | 2 | | | K00343 | B1 | E 050-099, 275-299 |

WIRE LIST

D280T132

91-21-11
Section W0170
Page 53
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | | |
| 774 | 12 | | PA | | 6-0 | 21-58-14 | D06286J | | | | 2 | | | K00343 | B1 | E | | 150-199 |
| 775 | 12 | | PA | | 7-0 | 21-58-14 | D06286J | | | | 3 | | | K00343 | C1 | E | | 050-099, 275-299 |
| 775 | 12 | | PA | | 6-0 | 21-58-14 | D06286J | | | | 3 | | | K00343 | C1 | E | | 150-199 |
| 776 | 24 | | PK | | 5-0 | 21-44-21 | D05060J | | | | 7 | | | TB0302X | C002 | BJ | | 050-099, 275-299 |
| 776 | 24 | | PK | | 4-0 | 21-44-21 | D05060J | | | | 7 | | | TB0302X | C002 | BJ | | 150-199 |
| 77F | 20 | | PA | | 5-0 | 36-23-11 | D05308J | | | | 24 | | | D06286J | | 6 | | 050-099, 162 |
| 77F | 20 | | PA | | 4-0 | 36-23-11 | D05308J | | | | 24 | | | D06286J | | 6 | | 156-157, 166-199, 277-299 |
| 77P | 24 | | PK | | 5-0 | 26-18-11 | D03554 | | | | 5 | | | D05306J | | 30 | | ALL |
| 77Q | 20 | | PA | | 3-0 | 26-18-11 | D03554 | | | | 4 | | | GDY0006 | D.. | 2 | | ALL |
| 787 | 24 | | PK | | 5-0 | 34-61-14 | D03610 | | | | 7 | | | D05433J | | 21 | | ALL |
| 788 | 20 | | PA | | 3-0 | 34-61-14 | D03610 | | | | 8 | | | GDY0006 | D.. | 2 | | 050-099, 275-299 |
| 788 | 20 | | PA | | 2-0 | 34-61-14 | D03610 | | | | 8 | | | GDY0006 | D.. | 2 | | 150-199 |
| 78A | 22 | | PA | | 2-0 | 21-66-11 | TB0318D | | | C004 | 2 | | | TB0318D | C001 | 2 | | 050-099, 162-199 |
| 78F | 20 | | PA | | 5-0 | 36-23-11 | D05308J | | | | 26 | | | D06286J | | 7 | | 050-099, 162 |
| 78F | 20 | | PA | | 4-0 | 36-23-11 | D05308J | | | | 26 | | | D06286J | | 7 | | 156-157, 166-199, 277-299 |
| 793 | 18 | | PA | | 6-0 | 28-41-12 | D00340 | | | | A1 | | | TB0218G | | 19 | 2 | ALL |
| 794 | 18 | | PQ | CW | 6-0 | 28-41-12 | D00340 | | | | B3 | | | TB0216F | A007 | | 2 | ALL |
| 794Z | | | | CW | 0-0 | 28-41-12 | D00340 | | | | DED | | | TB0216F | DED | | | ALL |
| 795 | 18 | | PQ | CX | 6-0 | 28-41-12 | D00340 | | | | B1 | | | TB0272G | | 7 | 2 | ALL |
| 795Z | | | | CX | 0-0 | 28-41-12 | D00340 | | | | DED | | | TB0272G | DED | | | ALL |
| 796 | 24 | | PK | | 3-0 | 29-32-11 | D04932J | | | | 30 | | | D05360J | | 18 | | ALL |
| 797 | 24 | | PV | BX | 6-0 | 32-09-11 | M01161 | | | | B | C | | D04672J | | 23 | | 050-099, 275-299 |
| 797 | 24 | | PV | BX | 5-0 | 32-09-11 | M01161 | | | | B | C | | D04672J | | 23 | | 150-199 |
| 797Z | | | | BX | 0-0 | 32-09-11 | M01161 | | | | DED | | | D04672J | DED | | | ALL |
| 798 | 20 | | PA | | 3-0 | 32-09-11 | D01736 | | | | A1 | | | GDY0004 | D.. | 2 | | ALL |
| 79A | 22 | | PA | | 10-0 | 21-66-11 | TB0076Z | | | | 13 | BJ | | D13842 | X1 | | | 050-099, 162-199 |
| 79F | 20 | | PA | | 5-0 | 36-23-11 | D05308J | | | | 25 | | | D06286J | | 8 | | 050-099, 162 |
| 79F | 20 | | PA | | 4-0 | 36-23-11 | D05308J | | | | 25 | | | D06286J | | 8 | | 156-157, 166-199, 277-299 |
| 801 | 20 | | PA | | 6-0 | 21-45-11 | D01612 | | | | D1 | | | TB0222X | A001 | BJ | | ALL |
| 802 | 24 | | PK | | 6-0 | 36-11-61 | D04904J | | | | 39 | | | TB0260Y | A005 | BJ | | 050-099, 156, 162-166 |
| 802 | 24 | | PK | | 6-0 | 36-11-61 | D04904J | | | | 39 | | | TB0260Z | 4 | BJ | | 150-154 |
| 802 | 24 | | PK | | 3-0 | 36-11-61 | D04904J | | | | 39 | | | TB0260Y | A005 | BJ | | 155 |
| 802 | 24 | | PK | | 6-0 | 36-11-61 | D04904J | | | | 39 | | | TB0318Y | C015 | BJ | | 157, 167-199 |
| 802 | 24 | | PK | | 6-0 | 36-11-61 | TB0260Z | | | | 4 | BJ | | D04904J | | 39 | | 275 |
| 802 | 24 | | PK | | 6-0 | 36-11-61 | TB0260Y | | | | A005 | BJ | | D04904J | | 39 | | 276 |
| 802 | 24 | | PK | | 6-0 | 36-11-61 | TB0318Y | | | | C015 | BJ | | D04904J | | 39 | | 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 54

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 803 | 24 | | PK | 3-0 | 36-11-61 | D04904J | | 38 | | | D05780J | 23 | | | 050-099 |
| 803 | 24 | | PK | 4-0 | 36-11-61 | D05780J | | 23 | | | D04904J | 38 | | | 150-199 |
| 803 | 24 | | PK | 3-0 | 36-11-61 | D05780J | | 23 | | | D04904J | 38 | | | 275-299 |
| 804 | 22 | | PA | 8-0 | 36-11-61 | D04904J | | 37 | | | TB0218Y | C013 | BJ | | 050-099 |
| 804 | 22 | | PA | 8-0 | 36-11-61 | TB0218Y | | C013 | BJ | | D04904J | 37 | | | 150-155, 162-165, 275-276 |
| 804 | 22 | | PA | 5-0 | 36-11-61 | TB0218Y | | C13 | BJ | | D04904J | 37 | | | 156, 166 |
| 804 | 22 | | PA | 5-0 | 36-11-61 | TB0218Y | | C013 | BJ | | D04904J | 37 | | | 157, 167-199, 277-299 |
| 805 | 22 | | PA | 8-0 | 36-11-61 | D04904J | | 36 | | | TB0220Y | A002 | BJ | | 050-099, 150-154 |
| 805 | 22 | | PA | 8-0 | 36-11-61 | TB0220Y | | A002 | BJ | | D04904J | 36 | | | 155, 275-276 |
| 805 | 22 | | PA | 8-0 | 36-11-61 | TB0220Y | | A02 | BJ | | D04904J | 36 | | | 156, 162-166 |
| 805 | 22 | | PA | 5-0 | 36-11-61 | TB0220Y | | A002 | BJ | | D04904J | 36 | | | 157, 167-199, 277-299 |
| 806 | 20 | | PA | 3-0 | 78-36-11 | D13040 | | A1 | | | GDX0012 | D.. | 2 | | ALL |
| 806R | 22 | | PH | 4-0 | 26-18-12 | D04672J | | 28 | | | D04932J | 33 | | | 050-099, 150-199 |
| 806R | 22 | | PH | 4-0 | 26-18-12 | D04932J | | 33 | | | D04672J | 28 | | | 275-299 |
| 807 | 20 | | PA | 3-0 | 78-36-11 | D13040 | | B3 | | | GDX0012 | D.. | 2 | | ALL |
| 807R | 22 | | PH | 4-0 | 26-18-12 | D04672J | | 29 | | | D04932J | 34 | | | 050-099, 150-199 |
| 807R | 22 | | PH | 4-0 | 26-18-12 | D04932J | | 34 | | | D04672J | 29 | | | 275-299 |
| 808 | 22 | | PA | 9-0 | 78-36-11 | D13040 | | B1 | | | TB0272Y | C006 | BJ | | 050-099 |
| 808 | 22 | | PA | 8-0 | 78-36-11 | D13040 | | B1 | | | TB0272Y | C006 | BJ | | 150-199, 275-299 |
| 809 | 24 | | PK | 6-0 | 78-34-11 | D05300J | | 18 | | | TB0318Z | 29 | BJ | | 050-099, 157, 167-199, 277-299 |
| 809 | 24 | | PK | 9-0 | 78-34-11 | D05300J | | 18 | | | TB0318Z | 29 | BJ | | 150-156, 162-166, 275-276 |
| 80H | 22 | | PA | 7-0 | 30-21-11 | D12126 | | 6 | | | D04338J | 6 | | | 050-099 |
| 80H | 22 | | PA | 7-0 | 30-21-11 | D04338J | | 6 | | | D12126 | 6 | | | 150-154 |
| 80H | 22 | | PA | 6-0 | 30-21-11 | D04338J | | 6 | | | D12126 | 6 | | | 155-199 |
| 80J | 22 | | PA | 7-0 | 30-21-11 | D12126 | | 4 | | | D04338J | 20 | | | 050-099 |
| 80J | 22 | | PA | 7-0 | 30-21-11 | D04338J | | 20 | | | D12126 | 4 | | | 150-154 |
| 80J | 22 | | PA | 6-0 | 30-21-11 | D04338J | | 20 | | | D12126 | 4 | | | 155-199 |
| 80K | 22 | | PA | 7-0 | 30-21-11 | D12126 | | 5 | | | D04338J | 5 | | | 050-099 |
| 80K | 22 | | PA | 7-0 | 30-21-11 | D04338J | | 5 | | | D12126 | 5 | | | 150-154 |
| 80K | 22 | | PA | 6-0 | 30-21-11 | D04338J | | 5 | | | D12126 | 5 | | | 155-199 |
| 80L | 22 | | PA | 4-0 | 30-21-11 | D05360J | | 20 | | | TB0222Z | 15 | BJ | | 050-099 |
| 80L | 22 | | PA | 7-0 | 30-21-11 | D05360J | | 20 | | | TB0222Z | 15 | BJ | | 150-154 |
| 80L | 22 | | PA | 6-0 | 30-21-11 | D05360J | | 20 | | | TB0222Z | 15 | BJ | | 155-199 |
| 80M | 22 | | PA | 4-0 | 30-21-11 | D04338J | | 7 | | | TB0222Z | 15 | BJ | | 050-099 |
| 80M | 22 | | PA | 7-0 | 30-21-11 | D04338J | | 7 | | | TB0222Z | 15 | BJ | | 150-154 |
| 80M | 22 | | PA | 6-0 | 30-21-11 | D04338J | | 7 | | | TB0222Z | 15 | BJ | | 155-199 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 55

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 80N | 22 | | PA | 5-0 | 30-21-11 | D12126 | | 7 | | | | | TB0222Z | 16 | BJ | | 050-099 |
| 80N | 22 | | PA | 7-0 | 30-21-11 | D12126 | | 7 | | | | | TB0222Z | 16 | BJ | | 150-154 |
| 80N | 22 | | PA | 6-0 | 30-21-11 | D12126 | | 7 | | | | | TB0222Z | 16 | BJ | | 155-199 |
| 80R | 22 | | PA | 5-0 | 30-21-11 | D12126 | | 2 | | | | | TB0222Z | 16 | BJ | | 050-099 |
| 80R | 22 | | PA | 7-0 | 30-21-11 | D12126 | | 2 | | | | | TB0222Z | 16 | BJ | | 150-154 |
| 80R | 22 | | PA | 6-0 | 30-21-11 | D12126 | | 2 | | | | | TB0222Z | 16 | BJ | | 155-199 |
| 80T | 22 | | PA | 5-0 | 30-21-11 | D12134 | | 7 | | | | | TB0222Z | 16 | BJ | | 050-099 |
| 80T | 22 | | PA | 7-0 | 30-21-11 | D12134 | | 7 | | | | | TB0222Z | 16 | BJ | | 150-154 |
| 80T | 22 | | PA | 6-0 | 30-21-11 | D12134 | | 7 | | | | | TB0222Z | 16 | BJ | | 155-199 |
| 80U | 22 | | PA | 8-0 | 30-21-11 | D12122 | | 9 | | | | | D04338J | 17 | | | 050-099 |
| 80U | 22 | | PA | 11-0 | 30-21-11 | D04338J | | 17 | | | | | D12122 | 9 | | | 150-154 |
| 80U | 22 | | PA | 10-0 | 30-21-11 | D04338J | | 17 | | | | | D12122 | 9 | | | 155-199 |
| 80V | 22 | | PA | 8-0 | 30-21-11 | D12122 | | 10 | | | | | D04338J | 16 | | | 050-099 |
| 80V | 22 | | PA | 11-0 | 30-21-11 | D04338J | | 16 | | | | | D12122 | 10 | | | 150-154 |
| 80V | 22 | | PA | 10-0 | 30-21-11 | D04338J | | 16 | | | | | D12122 | 10 | | | 155-199 |
| 80W | 22 | | PA | 4-0 | 30-21-11 | D12126 | | 3 | | | | | TB0250Y | C002 | BJ | | 050-099 |
| 80W | 22 | | PA | 6-0 | 30-21-11 | D12126 | | 3 | | | | | TB0250Y | C002 | BJ | | 150-154 |
| 80W | 22 | | PA | 5-0 | 30-21-11 | D12126 | | 3 | | | | | TB0250Y | C002 | BJ | | 155-199 |
| 80X | 22 | | PA | 4-0 | 30-21-11 | D12134 | | 1 | | | | | TB0250Y | C002 | BJ | | 050-099 |
| 80X | 22 | | PA | 6-0 | 30-21-11 | D12134 | | 1 | | | | | TB0250Y | C002 | BJ | | 150-154 |
| 80X | 22 | | PA | 5-0 | 30-21-11 | D12134 | | 1 | | | | | TB0250Y | C002 | BJ | | 155-199 |
| 80Y | 20 | | PA | 4-0 | 30-21-11 | D12134 | | 6 | | | | | GDX0017 | D.. | 2 | * | 050-099 |
| 80Y | 20 | | PA | 6-0 | 30-21-11 | D12134 | | 6 | | | | | GDX0017 | D.. | 2 | * | 150-154 |
| 80Y | 20 | | PA | 5-0 | 30-21-11 | D12134 | | 6 | | | | | GDX0017 | D.. | 2 | * | 155-199 |
| 810 | 22 | | PA | 9-0 | 78-36-11 | D13040 | | X1 | | | | | TB0272Y | C006 | BJ | | 050-099 |
| 810 | 22 | | PA | 8-0 | 78-36-11 | D13040 | | X1 | | | | | TB0272Y | C006 | BJ | | 150-199, 275-299 |
| 811 | 24 | | PK | 4-0 | 78-34-11 | D05300J | | 17 | | | | | TB0220Y | C002 | BJ | | ALL |
| 812 | 24 | | PK | 8-0 | 78-34-11 | D03492 | | X1 | | | | | TB0076Z | 10 | BJ | | 050-099, 275-299 |
| 812 | 24 | | PK | 7-0 | 78-34-11 | D03492 | | X1 | | | | | TB0076Z | 10 | BJ | | 150-199 |
| 813 | 24 | | PK | 8-0 | 78-34-11 | D03492 | | B2 | | | | | TB0076Z | 10 | BJ | | 050-099, 275-299 |
| 813 | 24 | | PK | 7-0 | 78-34-11 | D03492 | | B2 | | | | | TB0076Z | 10 | BJ | | 150-199 |
| 814 | 22 | | PA | 12-0 | 78-34-11 | D03492 | | B1 | | | | | D20102 | B3 | | | ALL |
| 815 | 24 | | PK | 6-0 | 78-34-11 | D03492 | | X2 | | | | | D05300J | 19 | | | ALL |
| 817 | 22 | | PA | 9-0 | 78-36-11 | D13040 | | X2 | | | | | TB0272X | B001 | BJ | | 050-099 |
| 817 | 22 | | PA | 10-0 | 78-36-11 | D13040 | | X2 | | | | | TB0272X | B001 | BJ | | 150-199 |
| 817 | 22 | | PA | 8-0 | 78-36-11 | D13040 | | X2 | | | | | TB0272X | B001 | BJ | | 275-299 |
| 818 | 22 | | PQ | R8 | 4-0 | 78-36-11 | TB0272X | | B001 | BJ | | | D05306J | 9 | | | 050-099 |
| 818 | 22 | | PQ | CO | 5-0 | 78-36-11 | TB0272X | | B001 | BJ | | | D05306J | 9 | | | 150-199 |
| 818 | 22 | | PQ | CO | 6-0 | 78-36-11 | TB0272X | | B001 | BJ | | | D05306J | 9 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 56

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 818Z | | | | R8 | 0-0 | 78-36-11 | TB0272X | DED | | | D05306J | | | | R8 | 050-099 |
| 818Z | | | | CO | 0-0 | 78-36-11 | TB0272X | DED | | | D05306J | | \$ | | FT | 150-199 |
| 818Z | | | | CO | 0-0 | 78-36-11 | TB0272X | DED | | | D05306J | | | | FT | 275-299 |
| 819 | 22 | | PA | | 3-0 | 78-36-11 | D05360J | | 15 | | D05300J | | 47 | | | 050-099 |
| 819 | 22 | | PA | | 3-0 | 78-36-11 | D05300J | | 47 | | D05360J | | 15 | | | 150-199, 275-299 |
| 81A | 20 | | PA | | 4-0 | 30-21-11 | D12134 | | 2 | | GD0017 | | D.. | 2 | * | 050-099 |
| 81A | 20 | | PA | | 6-0 | 30-21-11 | D12134 | | 2 | | GD0017 | | D.. | 2 | * | 150-154 |
| 81A | 20 | | PA | | 5-0 | 30-21-11 | D12134 | | 2 | | GD0017 | | D.. | 2 | * | 155-199 |
| 81C | 24 | | PK | | 5-0 | 30-21-11 | D12134 | | 5 | | TB0216X | | A004 | BJ | | 050-099, 155-199 |
| 81C | 24 | | PK | | 6-0 | 30-21-11 | D12134 | | 5 | | TB0216X | | A004 | BJ | | 150-154 |
| 81D | 24 | | PK | | 6-0 | 30-21-11 | D12134 | | 3 | | D04709J | | 14 | | | 050-099 |
| 81D | 24 | | PK | | 9-0 | 30-21-11 | D12134 | | 3 | | D04709J | | 13 | | | 150-154 |
| 81D | 24 | | PK | | 8-0 | 30-21-11 | D12134 | | 3 | | D04709J | | 14 | | | 155-199 |
| 81E | 22 | | PA | | 9-0 | 30-21-11 | D12122 | | 6 | | TB0222Z | | 15 | BJ | | 050-099, 150-154 |
| 81E | 22 | | PA | | 8-0 | 30-21-11 | D12122 | | 6 | | TB0222Z | | 15 | BJ | | 155-199 |
| 81F | 22 | | PA | | 5-0 | 30-21-11 | D12126 | | 1 | | TB0222Z | | 15 | BJ | | 050-099 |
| 81F | 22 | | PA | | 7-0 | 30-21-11 | D12126 | | 1 | | TB0222Z | | 15 | BJ | | 150-154 |
| 81F | 22 | | PA | | 6-0 | 30-21-11 | D12126 | | 1 | | TB0222Z | | 15 | BJ | | 155-199 |
| 81G | 20 | | PA | | 4-0 | 30-21-11 | D12130 | | 8 | | GD0017 | | D.. | 2 | | 050-099 |
| 81G | 20 | | PA | | 6-0 | 30-21-11 | D12130 | | 8 | | GD0017 | | D.. | 2 | | 150-154 |
| 81G | 20 | | PA | | 5-0 | 30-21-11 | D12130 | | 8 | | GD0017 | | D.. | 2 | | 155-199 |
| 81H | 24 | | PK | | 6-0 | 30-21-11 | D05658J | | 2 | | TB0250Y | | C002 | BJ | | 050-099 |
| 81H | 24 | | PK | | 10-0 | 30-21-11 | D05658J | | 2 | | TB0250Y | | C002 | BJ | | 150-154 |
| 81H | 24 | | PK | | 9-0 | 30-21-11 | D05658J | | 2 | | TB0250Y | | C002 | BJ | | 155-199 |
| 81J | 22 | | PA | | 12-0 | 30-21-11 | D12122 | | 1 | | D12130 | | 3 | | | 050-099, 155-199 |
| 81J | 22 | | PA | | 13-0 | 30-21-11 | D12122 | | 1 | | D12130 | | 3 | | | 150-154 |
| 81K | 20 | | PA | | 12-0 | 30-21-11 | D12122 | | 12 | | GD0017 | | D.. | 2 | * | 050-099, 155-199 |
| 81K | 20 | | PA | | 13-0 | 30-21-11 | D12122 | | 12 | | GD0017 | | D.. | 2 | * | 150-154 |
| 81L | 24 | | PK | | 8-0 | 73-21-16 | D05832J | | 1 | | D12122 | | 4 | | | 050-099 |
| 81L | 24 | | PK | | 11-0 | 73-21-16 | D05832J | | 1 | | D12122 | | 4 | | | 150-154 |
| 81L | 24 | | PK | | 10-0 | 73-21-16 | D05832J | | 1 | | D12122 | | 4 | | | 155-199 |
| 81M | 22 | | PA | | 12-0 | 30-21-11 | D12122 | | 11 | | D12130 | | 7 | | | 050-099 |
| 81M | 22 | | PA | | 13-0 | 30-21-11 | D12130 | | 7 | | D12122 | | 11 | | | 150-154 |
| 81M | 22 | | PA | | 12-0 | 30-21-11 | D12130 | | 7 | | D12122 | | 11 | | | 155-199 |
| 81P | 22 | | PA | | 10-0 | 73-21-19 | D12122 | | 7 | | D20542 | | 13 | | | 050-099 |
| 81P | 22 | | PA | | 12-0 | 73-21-19 | D12122 | | 7 | | D20542 | | 13 | | | 150-199 |
| 81R | 20 | | PA | | 12-0 | 73-21-16 | D12122 | | 5 | | GD0017 | | D.. | 2 | * | 050-099, 155-199 |
| 81R | 20 | | PA | | 13-0 | 73-21-16 | D12122 | | 5 | | GD0017 | | D.. | 2 | * | 150-154 |
| 81Z | 20 | | PQ | JS | 5-0 | 78-34-11 | D05894J | | 5 | | D05832J | | 50 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 57

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 81ZZ | | | | JS | 0-0 | 78-34-11 | D05894J | | 15 | | | | D05832J | 14 | | ALL |
| 820 | 24 | | PK | | 3-0 | 30-21-11 | D05360J | | 16 | | | | D05306J | 32 | | 050-099, 275-299 |
| 820 | 24 | | PK | | 3-0 | 30-21-11 | D05306J | | 32 | | | | D05306J | 16 | | 150-199 |
| 821 | 22 | | PA | | 3-0 | 30-21-11 | D04338J | | 5 | | | | D05306J | 25 | | 275-299 |
| 822 | 22 | | PA | | 8-0 | 30-21-11 | D12122 | | 2 | | | | D05306J | 25 | | 050-099 |
| 822 | 22 | | PA | | 11-0 | 30-21-11 | D12122 | | 2 | | | | D05306J | 25 | | 150-154 |
| 822 | 22 | | PA | | 10-0 | 30-21-11 | D12122 | | 2 | | | | D05306J | 25 | | 155-199 |
| 822 | 22 | | PA | | 3-0 | 30-21-11 | D04338J | | 6 | | | | D05306J | 28 | | 275-299 |
| 823 | 24 | | PK | | 4-0 | 30-21-11 | D04338J | | 18 | | | | TB0222Z | 16 | BJ | 050-099 |
| 823 | 24 | | PK | | 7-0 | 30-21-11 | D04338J | | 18 | | | | TB0222Z | 16 | BJ | 150-154 |
| 823 | 24 | | PK | | 6-0 | 30-21-11 | D04338J | | 18 | | | | TB0222Z | 16 | BJ | 155-199 |
| 823 | 24 | | PK | | 6-0 | 30-21-11 | D04338J | | 7 | | | | TB0250Y | C002 | BJ | 275-299 |
| 824 | 20 | | PA | | 3-0 | 28-41-12 | D00340 | | X2 | | | | GDX0004 | D.. | 2 | ALL |
| 825 | 22 | | PA | | 6-0 | 28-41-12 | D00340 | | X1 | | | | TB0272H | 10 | 2 | ALL |
| 826 | 18 | | PQ | CY | 6-0 | 28-41-12 | D00340 | | A2 | | | | TB0272G | 9 | 2 | ALL |
| 826Z | | | | CY | 0-0 | 28-41-12 | D00340 | | DED | | | | TB0272G | DED | | ALL |
| 827 | 18 | | PQ | AO | 6-0 | 28-41-12 | D00340 | | B2 | | | | TB0272G | 8 | 2 | ALL |
| 827Z | | | | AO | 0-0 | 28-41-12 | D00340 | | DED | | | | TB0272G | DED | | ALL |
| 828 | 18 | | PA | | 6-0 | 33-42-11 | D04338J | | 24 | DK | | | K00161 | A2 | E | 050-099 |
| 828 | 16 | | PA | | 6-0 | 33-42-11 | D04338J | | 24 | FM | | | K00161 | A2 | E | 150-199, 275-299 |
| 829 | 16 | | PA | | 7-0 | 33-42-11 | D04672J | | 48 | FL | | | K00435 | B2 | E | ALL |
| 82A | 22 | | PA | | 9-0 | 21-66-11 | D13844 | | A2 | | | | D13842 | X2 | | 050-099, 162-199 |
| 82B | 20 | | PA | | 10-0 | 78-34-11 | D03528 | | A2 | | | | D05832J | 6 | | ALL |
| 82FB | 24 | | PL | GO | 5-0 | 36-23-11 | D05780J | | 27 | | | | D04802J | 30 | | 050-099, 162 |
| 82FB | 24 | | PL | GO | 4-0 | 36-23-11 | D05780J | | 27 | | | | D04802J | 30 | | 156-157, 166-199, 277-299 |
| 82FR | 24 | | PL | GO | 0-0 | 36-23-11 | D05780J | | 26 | | | | D04802J | 14 | | 050-099, 156-162, 166-199, 277-299 |
| 82J | 22 | | PA | | 10-0 | 78-36-11 | D20092 | | D3 | | | | D05433J | 20 | | ALL |
| 82K | 22 | | PA | | 10-0 | 78-36-11 | D20092 | | D2 | | | | D05433J | 37 | | ALL |
| 82M | 22 | | PA | | 10-0 | 78-36-11 | D20092 | | B2 | | | | D05433J | 50 | | ALL |
| 82P | 22 | | PA | | 10-0 | 78-36-11 | D20092 | | C2 | | | | D05433J | 49 | | ALL |
| 82S | 20 | | PA | | 10-0 | 78-34-11 | D03528 | | A1 | | | | TB0302Y | C017 | BJ | ALL |
| 82V | 20 | | PA | | 10-0 | 78-34-11 | D03528 | | X1 | | | | D05300J | 13 | | ALL |
| 830 | 24 | | PK | | 7-0 | 33-42-11 | D04338J | | 15 | | | | K00435 | X1 | C | ALL |
| 831 | 22 | | PA | | 4-0 | 78-36-11 | D05300J | | 42 | | | | TB0272Y | C006 | BJ | 050-099 |
| 831 | 22 | | PA | | 6-0 | 78-36-11 | D05300J | | 42 | | | | TB0272Y | C006 | BJ | 275-299 |
| 832 | 20 | | PA | | 4-0 | 21-58-14 | SP01610 | | | W | | | GDX0008 | D.. | 2 | 050-099, 275-299 |
| 832 | 20 | | PA | | 3-0 | 21-58-14 | SP01610 | | | W | | | GDX0008 | D.. | 2 | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 58

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|---------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 833 | 24 | | PK | | 5-0 | 23-31-13 | D04709J | | | | TB0216X | D003 | BJ | | ALL |
| 834 | 22 | | PA | | 7-0 | 78-36-11 | D13040 | | A2 | | D05300J | 43 | | | 050-099 |
| 834 | 22 | | PA | | 7-0 | 78-36-11 | D05300J | | | | D13040 | A2 | | | 150-199, 275-299 |
| 835 | 22 | | PA | | 7-0 | 78-36-11 | D13040 | | B2 | | D05300J | 44 | | | 050-099 |
| 835 | 22 | | PA | | 7-0 | 78-36-11 | D05300J | | | | D13040 | B2 | | | 150-199, 275-299 |
| 836 | 24 | | PK | | 5-0 | 21-58-11 | D04662J | | | | TB0302Y | A024 | BJ | | 050-099, 150-155, 162-165, 275-276 |
| 836 | 24 | | PK | | 5-0 | 21-58-11 | D04662J | | | | TB0302Y | A036 | BJ | | 156-157, 166-199, 277-299 |
| 837 | 22 | | PA | | 9-0 | 78-36-11 | D13040 | | A3 | | TB0272Y | C006 | BJ | | 050-099 |
| 837 | 22 | | PA | | 8-0 | 78-36-11 | D13040 | | A3 | | TB0272Y | C006 | BJ | | 150-199, 275-299 |
| 838 | 20 | | UA | | 7-0 | 78-36-11 | GDX0012 | | S.. | 2 | D05306J | | | R8 | 050-099 |
| 838 | 20 | | UA | | 8-0 | 78-36-11 | GDX0012 | | S.. | 2 | D05306J | | | \$ | 150-199 |
| 838 | 20 | | UA | | 8-0 | 78-36-11 | GDX0012 | | S.. | 2 | D05306J | | | FT | 275-299 |
| 839 | 22 | | PA | | 10-0 | 30-21-11 | TB0080D | | A011 | 2 | TB0222Z | 15 | BJ | | 050-099 |
| 839 | 22 | | PA | | 11-0 | 30-21-11 | TB0222Z | | | 15 | TB0080D | A011 | 2 | | 150-154 |
| 839 | 22 | | PA | | 10-0 | 30-21-11 | TB0222Z | | | 15 | TB0080D | A011 | 2 | | 155-199 |
| 839 | 22 | | PA | | 10-0 | 30-21-11 | TB0250Y | | A002 | BJ | TB0080D | A011 | 2 | | 275-299 |
| 83A | 22 | | PA | | 10-0 | 21-66-11 | TB0076Z | | | 13 | D13842 | A2 | | | 050-099, 162-199 |
| 83B | 20 | | PQ | HZ | 7-0 | 78-34-11 | D05894J | | | 21 | TB0302Y | C017 | BJ | | 050-099 |
| 83B | 20 | | PQ | HZ | 8-0 | 78-34-11 | D05894J | | | 21 | TB0302Y | C017 | BJ | | 150-199, 275-299 |
| 83BZ | | | | HZ | 0-0 | 78-34-11 | D05894J | | | DED | TB0302Y | DED | | | ALL |
| 83M | 20 | | PA | | 10-0 | 78-36-11 | D20092 | | | B1 | GDX0006 | D.. | 2 | | ALL |
| 83N | 22 | | PA | | 10-0 | 78-36-11 | D20092 | | | C3 | D10164 | 2 | | | ALL |
| 83P | 20 | | PA | | 12-0 | 78-36-11 | D20092 | | | C1 | GDX0009 | D.. | 2 | | ALL |
| 83Q | 24 | | PK | | 10-0 | 78-34-11 | D03528 | | | X2 | D05832J | 38 | | | ALL |
| 83S | 20 | | PA | | 5-0 | 78-34-11 | D03528 | | | A3 | GDX0006 | D.. | 2 | | ALL |
| 83U | 24 | | PK | | 20-0 | 28-22-12 | D11631 | | | 4 | TB0216Y | C010 | BJ | | ALL |
| 83V | 24 | | PK | | 20-0 | 28-22-12 | D11631 | | | 7 | TB0216Z | 19 | BJ | | 050-099, 150-157, 275-278 |
| 83V | 24 | | PK | | 20-0 | 28-22-12 | D11631 | | | 7 | TB0216Z | 14 | BJ | | 162-199, 280-299 |
| 83Y | 24 | | PK | | 20-0 | 28-42-12 | D11631 | | | 3 | D11629 | 5 | | | ALL |
| 841 | 18 | | PA | | 6-0 | 33-42-21 | D05714J | | | 4 | D01948 | A1 | | | 050-099 |
| 841 | 18 | | PA | | 6-0 | 33-42-21 | D01948 | | | A1 | D05714J | 4 | | | 150-199, 275-299 |
| 844 | 20 | | PA | | 3-0 | 21-24-11 | GDX0008 | | | D.. | 2 | SP02680 | | W | 050-099 |
| 844 | 20 | | PA | | 3-0 | 21-24-11 | SP02680 | | | W | GDX0008 | D.. | 2 | | 150-199 |
| 846 | 24 | | PK | | 5-0 | 21-24-11 | TB0218Y | | A014 | BJ | SP02678 | | W | | 050-099 |
| 846 | 24 | | PK | | 6-0 | 21-24-11 | SP02678 | | | W | TB0218Y | A014 | BJ | | 150-199 |
| 847 | 24 | | PV | AL | 5-0 | 29-11-32 | D03536 | | | B1 | TB0216Y | A002 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 59

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 847Z | | | | AL | 0-0 | 29-11-32 | D03536 | | DED | | | | TB0216Y | DED | | | ALL |
| 849 | 24 | | PV | AP | 10-0 | 29-11-32 | D03536 | | B2 | | | | TB0078Z | 6 | BJ | | 050-099, 275-299 |
| 849 | 24 | | PV | AP | 9-0 | 29-11-32 | D03536 | | B2 | | | | TB0078Z | 6 | BJ | | 150-199 |
| 849Z | | | | AP | 0-0 | 29-11-32 | D03536 | | DED | | | | TB0078Z | DED | | | ALL |
| 84A | 22 | | PA | | 8-0 | 21-66-11 | D06934J | | 13 | | | | D13840 | A1 | | | 050-099, 162-199 |
| 84B | 22 | | PA | | 5-0 | 78-34-11 | D04709J | | 28 | | | | TB0220Y | C002 | BJ | | ALL |
| 84G | 20 | | PA | | 5-0 | 78-36-11 | D03492 | | C1 | | | | GDX0004 | D.. | 2 | | ALL |
| 84H | 22 | | PA | | 9-0 | 78-36-11 | D03492 | | C2 | | | | D05433J | 48 | | | 050-099 |
| 84H | 22 | | PA | | 8-0 | 78-36-11 | D03492 | | C2 | | | | D05433J | 48 | | | 150-199, 275-299 |
| 84J | 20 | | UA | | 10-0 | 78-34-11 | GDX0012 | | S.. | 2 | | | TB0318Z | | | HF | ALL |
| 850 | 22 | | PA | | 5-0 | 23-71-11 | D03536 | | A2 | | | | TB0218X | C002 | BJ | | ALL |
| 851 | 24 | | PK | | 5-0 | 21-53-12 | D03612 | | 1 | | | | TB0220X | B015 | BJ | | 050-099, 275-299 |
| 851 | 24 | | PK | | 4-0 | 21-53-12 | D03612 | | 1 | | | | TB0220X | B015 | BJ | | 150-199 |
| 852 | 20 | | PA | | 3-0 | 21-53-12 | D03612 | | 2 | | | | GDX0004 | D.. | 2 | | ALL |
| 853 | 24 | | PK | | 6-0 | 24-22-11 | D01612 | | C3 | | | | TB0216Y | A011 | BJ | | 050-099, 275-299 |
| 853 | 24 | | PK | | 5-0 | 24-22-11 | D01612 | | C3 | | | | TB0216Y | A011 | BJ | | 150-199 |
| 854 | 24 | | PK | | 6-0 | 21-24-11 | D05658J | | 43 | | | | SP01592 | | W | | 050-099, 150-199 |
| 855 | 24 | | PK | | 5-0 | 21-24-11 | D05658J | | 40 | | | | TB0218Y | A014 | BJ | | 050-099, 150-199 |
| 856 | 24 | | PK | | 5-0 | 21-24-11 | D05658J | | 41 | | | | TB0218X | C012 | BJ | | 050-099, 150-199 |
| 857 | 16 | | PA | | 7-0 | 33-42-11 | K00435 | | A2 | | | | D04672J | 20 | FL | | ALL |
| 858 | 20 | | PA | | 3-0 | 21-24-11 | GDX0008 | | D.. | 2 | | | SP01594 | | W | | 050-099 |
| 858 | 20 | | PA | | 3-0 | 21-24-11 | SP01594 | | | W | | | GDX0008 | D.. | 2 | | 150-199 |
| 85A | 22 | | PA | | 8-0 | 21-66-11 | D06934J | | 14 | | | | D13840 | A3 | | | 050-099, 162-199 |
| 85J | 24 | | PK | | 20-0 | 28-42-12 | D11629 | | 2 | | | | TB0218Y | A005 | BJ | | ALL |
| 85K | 22 | | PA | | 3-0 | 73-21-19 | TB0258D | | C006 | 2 | | | TB0258D | C005 | 2 | | 275-299 |
| 85P | 22 | | PA | | 8-0 | 73-21-19 | D20542 | | 1 | | | | TB0218Y | C007 | BJ | | 050-099, 150-199 |
| 85R | 20 | | PA | | 6-0 | 73-21-19 | D20542 | | 12 | | | | GDX0002 | D.. | 2 | | 050-099, 150-199 |
| 85T | 22 | | PA | | 12-0 | 73-21-19 | D05308J | | 11 | | | | D20542 | 6 | | | 050-099, 150-199 |
| 85T | 22 | | PA | | 12-0 | 74-31-11 | D05308J | | 11 | | | | TB0258D | A005 | 2 | | 275-299 |
| 85U | 24 | | PK | | 20-0 | 28-42-12 | D11629 | | 3 | | | | TB0218Y | C005 | BJ | | ALL |
| 85V | 24 | | PK | | 20-0 | 28-42-12 | D11631 | | 2 | | | | TB0218Y | C005 | BJ | | ALL |
| 85W | 24 | | PK | | 20-0 | 28-22-12 | D11629 | | 7 | | | | TB0216Z | 19 | BJ | | 050-099, 150-157, 275-278 |
| 85W | 24 | | PK | | 20-0 | 28-22-12 | D11629 | | 7 | | | | TB0216Z | 14 | BJ | | 162-199, 280-299 |
| 865 | 20 | | PA | | 6-0 | 73-21-19 | D03612 | | 4 | | | | GDX0015 | D.. | 2 | | ALL |
| 866 | 24 | | PK | | 4-0 | 24-22-11 | D05832J | | 8 | | | | TB0216Y | A011 | BJ | | 050-099, 275-299 |
| 866 | 24 | | PK | | 5-0 | 24-22-11 | D05832J | | 8 | | | | TB0216Y | A011 | BJ | | 150-199 |
| 867 | 24 | | PK | | 6-0 | 24-22-11 | D05658J | | 13 | | | | D01612 | C2 | | | ALL |
| 868 | 24 | | PK | | 5-0 | 24-22-11 | D03514 | | 13 | | | | TB0216Y | A011 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 60

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|----------|---------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 869R | 22 | | | PH | 4-0 | 26-17-11 | TB0302X | C005 | BJ | | D04932J | 11 | | | ALL |
| 86A | 22 | | | PA | 9-0 | 21-66-11 | D06934J | 15 | | | D13842 | A1 | | | 050-099, 162-199 |
| 86F | 24 | | | PK | 0-6 | 36-11-61 | TB0260Y | A005 | BJ | | TB0260D | A008 | 2 | | 050-099 |
| 86F | 24 | | | PK | 10-0 | 36-11-61 | TB0260Z | 4 | BJ | | TB0260D | A008 | 2 | | 150-154 |
| 86F | 24 | | | PK | 10-0 | 36-11-61 | TB0260Y | A005 | BJ | | TB0260D | A008 | 2 | | 155, 162-165 |
| 86F | 24 | | | PK | 2-0 | 36-11-61 | TB0260D | A008 | 2 | | TB0260Y | A005 | BJ | | 156, 166 |
| 86F | 24 | | | PK | 6-0 | 36-11-61 | TB0260Z | 4 | BJ | | TB0260D | A008 | 2 | | 275 |
| 86F | 24 | | | PK | 6-0 | 36-11-61 | TB0260Y | A005 | BJ | | TB0260D | A008 | 2 | | 276 |
| 86W | 20 | | | PA | 10-0 | 21-73-11 | C01131 | 2 | D | | D06934J | 3 | | | 275-299 |
| 871 | 22 | | | PA | 7-0 | 21-51-11 | D04672J | 46 | | | TB0076X | A001 | BJ | | ALL |
| 872 | 22 | | | PA | 7-0 | 21-51-11 | D04672J | 47 | | | TB0076X | B001 | BJ | | ALL |
| 874 | 22 | | | PA | 3-0 | 30-21-11 | D10160 | C2 | | | D11826 | A3 | | | 050-099, 155-199 |
| 874 | 22 | | | PA | 4-0 | 30-21-11 | D10160 | C2 | | | D11826 | A3 | | | 150-154 |
| 874 | 22 | | | PA | 3-0 | 30-21-11 | D10160 | C2 | | | TB0250Y | C002 | BJ | | 275-299 |
| 875 | 22 | | | PA | 5-0 | 74-31-11 | TB0222X | B007 | BJ | | D10160 | D1 | | * | 050-099 |
| 875 | 22 | | | PA | 5-0 | 74-31-11 | D10160 | D1 | | * | TB0222X | B007 | BJ | | 150-199, 275-299 |
| 876 | 22 | | | PA | 5-0 | 74-31-11 | D05308J | 14 | | | D10160 | D2 | | | ALL |
| 877 | 24 | | | PK | 3-0 | 33-16-14 | TB0076Y | C003 | BJ | | D03534 | 7 | | | ALL |
| 878 | 24 | | | PK | 6-0 | 33-16-14 | D04672J | 50 | | | D03534 | 8 | | | 050-099, 275-299 |
| 878 | 24 | | | PK | 7-0 | 33-16-14 | D04672J | 50 | | | D03534 | 8 | | | 150-199 |
| 879 | 20 | | | PA | 5-0 | 25-31-21 | D04672J | 61 | | | TB0272F | A012 | 2 | | 050-099, 150-199 |
| 879 | 18 | | | PA | 5-0 | 25-31-21 | D04672J | 61 | DL | | TB0272F | A012 | 2 | | 275-299 |
| 87A | 22 | | | PA | 9-0 | 21-66-11 | D06934J | 16 | | | D13842 | A3 | | | 050-099, 162-199 |
| 87F | 24 | | | PK | 3-0 | 27-28-11 | D05310J | 13 | | | D05360J | 1 | | | 155-157, 166-199, 277-299 |
| 880 | 20 | | | PA | 5-0 | 25-31-21 | D05894J | 8 | | | TB0272F | C012 | 2 | | 050-099, 150-199 |
| 880 | 18 | | | PA | 5-0 | 25-31-21 | D05894J | 18 | | | TB0272F | C012 | 2 | | 275-299 |
| 881 | 22 | | | PA | 4-0 | 30-21-11 | D10160 | X1 | | | TB0222Z | 15 | BJ | | 050-099 |
| 881 | 22 | | | PA | 7-0 | 30-21-11 | D10160 | X1 | | | TB0222Z | 15 | BJ | | 150-154 |
| 881 | 22 | | | PA | 6-0 | 30-21-11 | D10160 | X1 | | | TB0222Z | 15 | BJ | | 155-199 |
| 881 | 22 | | | PA | 3-0 | 30-21-11 | D10160 | X1 | | | TB0250Y | C002 | BJ | | 275-299 |
| 882 | 22 | | | PA | 5-0 | 30-21-11 | D10160 | C1 | | | D05306J | 26 | | | 050-099 |
| 882 | 22 | | | PA | 6-0 | 30-21-11 | D05306J | 26 | | | D10160 | C1 | | | 150-154 |
| 882 | 22 | | | PA | 5-0 | 30-21-11 | D05306J | 26 | | | D10160 | C1 | | | 155-199 |
| 882 | 22 | | | PA | 5-0 | 30-21-11 | D11826 | A3 | | | D05306J | 26 | | | 275-299 |
| 883 | 24 | | | PV | DG | 5-0 | 28-42-11 | D05360J | 11 | | TB0302Y | A012 | BJ | | ALL |
| 883Z | | | | DG | 0-0 | 28-42-11 | D05360J | DED | | | TB0302Y | DED | | | ALL |
| 884 | 22 | | | PQ | DH | 5-0 | 28-42-11 | D04932J | 2 | | TB0302Y | A012 | BJ | | ALL |
| 884Z | | | | DH | 0-0 | 28-42-11 | D04932J | DED | | | TB0302Y | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 61

Feb 06/2009

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 885 | 22 | PA | | | 5-0 | 79-33-11 | D05306J | | 42 | | | TB0302Y | C015 | BJ | | ALL |
| 886 | 22 | PA | | | 5-0 | 79-33-11 | D05306J | | 43 | | | TB0302Y | C015 | BJ | | ALL |
| 887 | 24 | PK | | | 5-0 | 79-33-11 | D05360J | | 51 | | | TB0302Y | C015 | BJ | | ALL |
| 888 | 22 | PA | | | 3-0 | 79-35-11 | D05306J | | 44 | | | D05360J | | 19 | | ALL |
| 889 | 24 | PK | | | 5-0 | 32-42-11 | D04904J | | 2 | | | TB0272F | C018 | 2 | | 050-099 |
| 889 | 24 | PK | | | 5-0 | 32-42-11 | D04904J | | 2 | | | TB0272X | C002 | BJ | | 150-199 |
| 889 | 24 | PK | | | 5-0 | 32-42-11 | D04904J | | 2 | | | TB0272X | A018 | BJ | | 275-299 |
| 88A | 22 | PA | | | 8-0 | 21-66-11 | TB0076Z | | 13 | BJ | | D13844 | | X1 | | 050-099, 162-199 |
| 88F | 24 | PK | | | 3-0 | 27-38-11 | D05360J | | 4 | | | D05312J | | 15 | | 155-157, 166-199, 277-299 |
| 890 | 24 | PK | | | 4-0 | 21-58-16 | D04906J | | 22 | | | TB0220X | A007 | BJ | | ALL |
| 891 | 24 | PK | | | 4-0 | 21-58-16 | D04906J | | 21 | | | TB0220X | B007 | BJ | | ALL |
| 892 | 24 | PK | | | 4-0 | 21-58-16 | D04906J | | 3 | | | TB0220X | C007 | BJ | | ALL |
| 894 | 16 | PA | | | 6-0 | 28-22-11 | D05930J | | 4 | | | K00190 | A2 | D | | 050-099, 275-299 |
| 894 | 16 | PA | | | 5-0 | 28-22-11 | D05930J | | 4 | | | K00190 | A2 | D | | 150-199 |
| 895 | 16 | PA | | | 6-0 | 28-22-11 | D05930J | | 5 | | | K00190 | B2 | D | | 050-099, 275-299 |
| 895 | 16 | PA | | | 5-0 | 28-22-11 | D05930J | | 5 | | | K00190 | B2 | D | | 150-199 |
| 896 | 16 | PA | | | 6-0 | 28-22-11 | D05930J | | 6 | | | K00190 | C2 | D | | 050-099, 275-299 |
| 896 | 16 | PA | | | 5-0 | 28-22-11 | D05930J | | 6 | | | K00190 | C2 | D | | 150-199 |
| 897 | 16 | PA | | | 6-0 | 28-22-11 | D05930J | | 7 | | | K00187 | A2 | D | | 050-099, 275-299 |
| 897 | 16 | PA | | | 5-0 | 28-22-11 | D05930J | | 7 | | | K00187 | A2 | D | | 150-199 |
| 898 | 16 | PA | | | 6-0 | 28-22-11 | D05930J | | 8 | | | K00187 | B2 | D | | 050-099, 275-299 |
| 898 | 16 | PA | | | 5-0 | 28-22-11 | D05930J | | 8 | | | K00187 | B2 | D | | 150-199 |
| 899 | 16 | PA | | | 6-0 | 28-22-11 | D05930J | | 9 | | | K00187 | C2 | D | | 050-099, 275-299 |
| 899 | 16 | PA | | | 5-0 | 28-22-11 | D05930J | | 9 | | | K00187 | C2 | D | | 150-199 |
| 89A | 24 | PK | | | 7-0 | 21-58-12 | D02886 | | | C3 | | TB0250X | A004 | BJ | | ALL |
| 89B | 24 | PK | | | 6-0 | 21-58-12 | D04802J | | 16 | | | TB0250X | B004 | BJ | | ALL |
| 89C | 24 | PK | | | 6-0 | 21-58-12 | D04904J | | 34 | | | TB0250Y | C008 | BJ | | ALL |
| 89D | 24 | PK | | | 6-0 | 21-58-12 | D04904J | | 35 | | | TB0250Y | A008 | BJ | | ALL |
| 89E | 24 | PK | | | 6-0 | 21-58-12 | D04904J | | 49 | | | TB0250Y | A007 | BJ | | ALL |
| 89F | 24 | PK | | | 6-0 | 21-58-12 | D04904J | | 51 | | | TB0250Y | C007 | BJ | | ALL |
| 89G | 24 | PK | | | 6-0 | 21-58-12 | D04802J | | 22 | | | TB0250X | D004 | BJ | | ALL |
| 89H | 24 | PK | | | 6-0 | 21-58-12 | D04904J | | 42 | | | TB0250Y | C010 | BJ | | ALL |
| 89J | 24 | PK | | | 6-0 | 21-58-12 | D04904J | | 43 | | | TB0250Y | A010 | BJ | | ALL |
| 89K | 24 | PK | | | 6-0 | 21-58-12 | D04802J | | 18 | | | TB0250X | C003 | BJ | | ALL |
| 89L | 24 | PK | | | 6-0 | 21-58-12 | TB0250X | | | D003 | BJ | D04802J | | 17 | | ALL |
| 908 | 22 | PA | | | 5-0 | 34-53-11 | TB0222Y | | | C016 | BJ | TB0222Y | C020 | BJ | | 275-299 |
| 909 | 22 | PA | | | 5-0 | 34-53-11 | TB0222Y | | | A016 | BJ | TB0222Y | A020 | BJ | | 275-299 |
| 90A | 20 | PA | | | 5-0 | 21-66-11 | D13844 | | | X2 | | GDX0009 | D.. | 2 | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 62

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 90F | 24 | | PK | | 3-0 | 27-38-11 | D05360J | | 3 | | D05312J | | 11 | | 155-157, 166-199, 277-299 |
| 910 | 22 | | PA | | 5-0 | 34-53-11 | TB0222Y | C015 | BJ | | TB0222Y | C019 | BJ | | 275-299 |
| 911B | 24 | | PW | DA | 0-0 | 34-53-11 | D05431J | | 8 | | TB0222Y | A016 | BJ | | 275-299 |
| 911R | 24 | | PW | DA | 5-0 | 34-53-11 | D05431J | | 7 | | TB0222Y | C016 | BJ | | 275-299 |
| 911Z | | | | DA | 0-0 | 34-53-11 | D05431J | | 4 | | TB0222Y | C015 | BJ | | 275-299 |
| 91C | 24 | | PV | DP | 5-0 | 73-21-14 | TB0302X | A001 | BJ | | D06582J | | 11 | | 050-099 |
| 91C | 24 | | PV | CI | 5-0 | 73-21-14 | TB0302X | A001 | BJ | | D06582J | | 11 | | 150-199, 275-299 |
| 91CZ | | | | DP | 0-0 | 73-21-14 | TB0302X | B002 | BJ | | D06582J | | | FH | 050-099 |
| 91CZ | | | | CI | 0-0 | 73-21-14 | TB0302X | B002 | BJ | | D06582J | | | FC | 150-199, 275-299 |
| 91F | 16 | | PQ | FM | 3-0 | 73-21-20 | D05832J | | 9 | FM | D06582J | | 2 | FM | 050-099 |
| 91F | 16 | | PQ | CJ | 3-0 | 73-21-20 | D05832J | | 9 | FL | D06582J | | 2 | FL | 150-199, 275-278 |
| 91F | 16 | | PQ | CJ | 3-0 | 73-21-20 | D05832J | | 9 | FL | D06582J | | 2 | FM | 280-299 |
| 91FZ | | | | FM | 0-0 | 73-21-20 | D05832J | | | | D06582J | | | FH | 050-099 |
| 91FZ | | | | CJ | 0-0 | 73-21-20 | D05832J | | | FA | D06582J | | | FC | 150-199, 277-299 |
| 91FZ | | | | CJ | 0-0 | 73-21-20 | D05832J | | 29 | F1 | D06582J | | 13 | | 275-276 |
| 91G | 24 | | PV | BN | 4-0 | 73-21-11 | D05832J | | 36 | | D04802J | | 26 | | 050-099 |
| 91G | 24 | | PV | BP | 4-0 | 73-21-11 | D05832J | | 36 | | D04802J | | 26 | | 150-199, 275-299 |
| 91GZ | | | | BN | 0-0 | 73-21-11 | D05832J | | 37 | | D04802J | | 29 | | 050-099 |
| 91GZ | | | | BP | 0-0 | 73-21-11 | D05832J | | 37 | | D04802J | | 29 | | 150-199, 275-299 |
| 91L | 24 | | PK | | 4-0 | 76-11-11 | D11752 | | Y1 | | TB0272Y | C005 | BJ | | 050-099 |
| 91L | 22 | | PA | | 5-0 | 76-11-11 | TB0272Y | C005 | BJ | | D11752 | | Y1 | | 150-199, 275-299 |
| 92A | 24 | | PK | | 1-0 | 36-11-61 | D04662J | | 35 | | D04662J | | 1 | | 050-099 |
| 92A | 24 | | PK | | 1-0 | 36-11-61 | D04662J | | 1 | | D04662J | | 35 | | 150-156, 162-166, 275-276 |
| 92B | 20 | | PA | | 3-0 | 36-11-61 | GDX0015 | D.. | 2 | | D01983 | | A2 | | 050-099 |
| 92B | 20 | | PA | | 3-0 | 36-11-61 | D01983 | | A2 | | GDX0015 | | D.. | 2 | 150-156, 162-166, 275-276 |
| 92C | 24 | | PK | | 3-0 | 36-11-61 | D01989 | | X2 | | D01983 | | A3 | | 050-099 |
| 92C | 24 | | PK | | 3-0 | 36-11-61 | D01983 | | A3 | | TB0260Y | C005 | BJ | | 150-154, 275 |
| 92C | 24 | | PK | | 3-0 | 36-11-61 | D01983 | | A3 | | D01989 | | X2 | | 155-156, 162-166, 276 |
| 92D | 24 | | PK | | 3-0 | 36-11-61 | TB0260Z | | 3 | BJ | D01983 | | X1 | | 050-099 |
| 92D | 24 | | PK | | 3-0 | 36-11-61 | D01983 | | X1 | | TB0260Z | | 3 | BJ | 150-155, 162-165, 275-276 |
| 92D | 24 | | PK | | 4-0 | 36-11-61 | D01983 | | X1 | | TB0260Z | | 3 | BJ | 156, 166 |
| 92R | 24 | | PK | | 3-0 | 36-11-61 | TB0260Z | | 3 | BJ | D01989 | | A1 | | 050-099 |
| 92R | 24 | | PK | | 3-0 | 36-11-61 | D01989 | | A1 | | TB0260Z | | 3 | BJ | 150-155, 162-165, 275-276 |
| 92R | 24 | | PK | | 4-0 | 36-11-61 | D01989 | | A1 | | TB0260Z | | 3 | BJ | 156, 166 |

WIRE LIST
D280T132

91-21-11
Section W0170
Page 63
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | |
| 92S | 24 | | PK | 3-0 | 36-11-61 | TB0260Y | A006 | BJ | | D01989 | A2 | | | 050-099 | | |
| 92S | 24 | | PK | 3-0 | 36-11-61 | D01989 | A2 | | | TB0260Y | A006 | BJ | | 150-155, 162-165, 275-276 | | |
| 92S | 24 | | PK | 4-0 | 36-11-61 | D01989 | A2 | | | TB0260Y | A006 | BJ | | 156, 166 | | |
| 92T | 24 | | PK | 3-0 | 36-11-61 | TB0260Y | A005 | BJ | | D01989 | B1 | | | 050-099 | | |
| 92T | 24 | | PK | 3-0 | 36-11-61 | D01989 | B1 | | | TB0260Z | 4 | BJ | | 150-154, 275 | | |
| 92T | 24 | | PK | 3-0 | 36-11-61 | D01989 | B1 | | | TB0260Y | A005 | BJ | | 155, 162-165, 276 | | |
| 92T | 24 | | PK | 4-0 | 36-11-61 | D01989 | B1 | | | TB0260Y | A005 | BJ | | 156, 166 | | |
| 92U | 20 | | PA | 3-0 | 36-11-61 | GDX0015 | D.. | 2 | | D01989 | B2 | | | 050-099 | | |
| 92U | 20 | | PA | 3-0 | 36-11-61 | D01989 | B2 | | | GDX0015 | D.. | 2 | | 150-156, 162-166, 275-276 | | |
| 92V | 24 | | PK | 3-0 | 36-11-61 | TB0260Y | A006 | BJ | | D01989 | X1 | | | 050-099 | | |
| 92V | 24 | | PK | 3-0 | 36-11-61 | D01989 | X1 | | | TB0260Y | A006 | BJ | | 150-155, 162-165, 275-276 | | |
| 92V | 24 | | PK | 4-0 | 36-11-61 | D01989 | X1 | | | TB0260Y | A006 | BJ | | 156, 166 | | |
| 92W | 24 | | PK | 3-0 | 36-11-61 | D01989 | X2 | | | TB0260Y | C005 | BJ | | 150-154, 275 | | |
| 92X | 24 | | PK | 3-0 | 36-11-61 | TB0260Z | 3 | BJ | | D01991 | A1 | | | 050-099 | | |
| 92X | 24 | | PK | 3-0 | 36-11-61 | D01991 | A1 | | | TB0260Z | 3 | BJ | | 150-155, 162-165, 275-276 | | |
| 92X | 24 | | PK | 4-0 | 36-11-61 | D01991 | A1 | | | TB0260Z | 3 | BJ | | 156, 166 | | |
| 92Y | 24 | | PK | 3-0 | 36-11-61 | TB0260Y | A006 | BJ | | D01991 | A2 | | | 050-099 | | |
| 92Y | 24 | | PK | 3-0 | 36-11-61 | D01991 | A2 | | | TB0260Y | A006 | BJ | | 150-155, 162-165, 275-276 | | |
| 92Y | 24 | | PK | 4-0 | 36-11-61 | D01991 | A2 | | | TB0260Y | A006 | BJ | | 156, 166 | | |
| 92Z | 24 | | PK | 6-0 | 36-11-61 | D04904J | 40 | | | D10160 | A2 | | | 050-099 | | |
| 92Z | 24 | | PK | 6-0 | 36-11-61 | D10160 | A2 | | | D04904J | 40 | | | 150-156, 162-166, 275-276 | | |
| 92Z | 24 | | PK | 5-0 | 36-11-61 | D10160 | A2 | | | D04904J | 40 | | | 157, 167-199, 277-299 | | |
| 93A | 20 | | PA | 3-0 | 36-11-61 | GDX0015 | D.. | 2 | | D01991 | B2 | | | 050-099 | | |
| 93A | 20 | | PA | 3-0 | 36-11-61 | D01991 | B2 | | | GDX0015 | D.. | 2 | | 150-156, 162-166, 275-276 | | |
| 93B | 24 | | PK | 3-0 | 36-11-61 | TB0260Z | 3 | BJ | | D01991 | X1 | | | 050-099 | | |
| 93B | 24 | | PK | 3-0 | 36-11-61 | D01991 | X1 | | | TB0260Z | 3 | BJ | | 150-155, 162-165, 275-276 | | |
| 93B | 24 | | PK | 4-0 | 36-11-61 | D01991 | X1 | | | TB0260Z | 3 | BJ | | 156, 166 | | |
| 93D | 24 | | PK | 6-0 | 36-11-61 | D05780J | 10 | | | TB0272G | 42 | 2 | | 050-099, 155, 162-165 | | |
| 93D | 24 | | PK | 6-0 | 36-11-61 | D05780J | 10 | | | TB0260Y | A005 | BJ | | 150-154, 275 | | |
| 93D | 24 | | PK | 4-0 | 36-11-61 | D05780J | 10 | | | TB0272G | 42 | 2 | | 156, 166 | | |
| 93D | 24 | | PK | 6-0 | 36-11-61 | D05780J | 10 | | | TB0260Y | A006 | BJ | | 157, 167-199, 277-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 64

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|---------------------------------------|----|------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0176 | 286T0176 | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 93D | 24 | | PK | 6-0 | 36-11-61 | D05780J | | 10 | | | TB0272D | C042 | 2 | | 276 |
| 93E | 24 | | PK | 6-6 | 36-11-61 | D05308J | | 41 | | | TB0260D | C008 | 2 | | 050-099 |
| 93E | 24 | | PK | 6-0 | 36-11-61 | D05308J | | 41 | | | TB0260D | C008 | 2 | | 150-155, 162-166 |
| 93E | 24 | | PK | 6-0 | 36-11-61 | TB0260D | | C008 | 2 | | D05308J | 41 | | | 156, 275-276 |
| 93F | 24 | | PK | 5-0 | SPARE | TB0260Y | | A005 | BJ | | TB0272D | CAP | Y | | 150-154 |
| 93F | 24 | | PK | 5-0 | 36-11-61 | TB0272D | | CAP | Y | | TB0260Y | A005 | BJ | | 275 |
| 93G | 24 | | PK | 4-0 | 36-11-61 | D04662J | | 49 | | | TB0272G | 42 | 2 | | 050-099 |
| 93G | 24 | | PK | 5-0 | 36-11-61 | TB0272G | | 42 | 2 | | D04662J | 49 | | | 150-156, 162-166 |
| 93G | 24 | | PK | 7-0 | 36-11-61 | TB0260Y | | A006 | BJ | | D04662J | 49 | | | 157, 167-199 |
| 93G | 24 | | PK | 8-0 | 36-11-61 | D04662J | | 49 | | | TB0260Y | A005 | BJ | | 275 |
| 93G | 24 | | PK | 5-0 | 36-11-61 | D04662J | | 49 | | | TB0272G | 42 | 2 | | 276 |
| 93G | 24 | | PK | 7-0 | 36-11-61 | D04662J | | 49 | | | TB0260Y | A006 | BJ | | 277-299 |
| 93P | 24 | | PK | 10-0 | 36-11-61 | TB0272D | | CAP | Y | | TB0080Y | C006 | BJ | | 150-154 |
| 93P | 24 | | PK | 8-0 | SPARE | TB0272D | | CAP | Y | | TB0080Y | C006 | BJ | | 275 |
| 94A | 22 | | PA | 7-0 | 21-66-11 | D13844 | | C1 | | | TB0318D | A001 | 2 | | 050-099, 162-199 |
| 95A | 22 | | PA | 5-0 | 21-66-11 | D05930J | | 1 | | | TB0318D | C001 | 2 | | 050-099, 162-199 |
| 96A | 20 | | PA | 5-0 | 21-66-11 | D13844 | | A1 | | | GDX0009 | D.. | 2 | | 050-099, 162-199 |
| 97A | 22 | | PA | 6-0 | 21-66-11 | D13844 | | A3 | | | D06934J | 17 | | | 050-099, 162-199 |
| 98A | 20 | | PA | 5-0 | 21-66-11 | D13844 | | B1 | | | GDX0009 | D.. | 2 | | 050-099, 162-199 |
| 99A | 20 | | PA | 5-0 | 34-22-16 | D03532 | | 1 | | | GDX0008 | S.. | 2 | | ALL |
| 99B | 22 | | PA | 6-0 | 34-22-16 | D05433J | | 19 | | | D03532 | 2 | | | 050-099 |
| 99B | 22 | | PA | 6-0 | 34-22-16 | D03532 | | 2 | | | D05433J | 19 | | | 150-199, 275-299 |
| A-A | | | | 0-0 | 21-25-11 | TS0192 | | 5 | | | SP01596 | | W | | ALL |
| A-B | | | | 0-0 | 21-25-11 | TS0192 | | 4 | | | SP01598 | | W | | ALL |
| A-C | | | | 0-0 | 21-58-14 | TS0102 | | 1 | | | SP01608 | | W | | ALL |
| A-D | | | | 0-0 | 21-58-14 | TS0102 | | 2 | | | SP01610 | | W | | ALL |
| A-E | | | | 0-0 | 21-26-11 | TS0246 | | 1 | | | SP01620 | | W | | ALL |
| A-F | | | | 0-0 | 21-26-11 | TS0246 | | 2 | | | SP01622 | | W | | ALL |
| A-G | | | | 0-0 | 21-25-11 | TS0192 | | 1 | | | SP02258 | | W | | ALL |
| A-H | | | | 0-0 | 21-25-11 | TS0192 | | 3 | | | SP02256 | | W | | ALL |
| A-I | | | | 0-0 | 21-66-11 | TS0524 | | 1 | | | SP04058 | | W | | 050-099, 162-199 |
| A-K | | | | 0-0 | 21-25-11 | TS0192 | | 2 | | | SP02260 | | W | | ALL |
| A-M | | | | 0-0 | 21-24-11 | TS0289 | | 1 | | | SP02678 | | W | | 050-099, 150-199 |
| A-N | | | | 0-0 | 21-24-11 | TS0289 | | 2 | | | SP02680 | | W | | 050-099, 150-199 |
| A-O | | | | 0-0 | 21-66-11 | TS0524 | | 2 | | | SP04060 | | W | | 050-099, 162-199 |
| A-P | | | | 0-0 | 21-24-11 | TS0289 | | 3 | | | SP01592 | | W | | 050-099, 150-199 |
| A-Q | | | | 0-0 | 21-24-11 | TS0289 | | 4 | | | SP01594 | | W | | 050-099, 150-199 |
| A-R | | | | 0-0 | 21-24-11 | TS0289 | | 5 | | | TS0289 | CAP | Y | | 050-099, 150-199 |
| A-S | | | | 0-0 | 21-66-11 | TS0524 | | 3 | | | SP04064 | CAP | Y | | 050-099, 162-199 |

WIRE LIST
D280T132

91-21-11
Section W0170
Page 65
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0176 | 286T0176 | | | P36-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| A-T | | | | 0-0 | 21-66-11 | TS0524 | | | 4 | | | | SP04062 | | W | | 050-099, 162-199 |
| A-U | | | | 0-0 | 21-66-11 | TS0524 | | | 5 | | | | SP04064 | | W | | 050-099, 162-199 |
| B-H | | | | 0-0 | 21-66-31 | TS0526 | | | 2 | | | | SP04076 | | W | | 050-099, 150, 152-199 |
| B-I | | | | 0-0 | 21-66-31 | TS0526 | | | 1 | | | | SP04074 | | W | | 050-099, 150, 152-199 |
| B-L | | | | 0-0 | 21-66-31 | TS0526 | | | 4 | | | | SP04078 | | W | | 050-099, 150, 152-199 |
| B-M | | | | 0-0 | 21-66-31 | TS0526 | | | 5 | | | | SP04080 | CAP | Y | | 050-099 |
| B-M | | | | 0-0 | 21-66-31 | TS0526 | | | 5 | | | | SP04080 | | W | | 150, 152-199 |
| B-N | | | | 0-0 | 21-66-31 | TS0526 | | | 3 | | | | SP04080 | | W | | 050-099 |
| B-N | | | | 0-0 | 21-66-31 | TS0526 | | | 3 | | | | SP04080 | CAP | Y | | 150, 152-199 |
| FR1 | | | | 0-0 | 73-21-11 | D05832J | | | | | | | D05832J | | | 29 | 150-199, 280-299 |
| FR3 | | | | 0-0 | 73-21-11 | D06582J | | | | | | | D06582J | | | 16 | 150-199, 275-299 |
| FR4 | | | | 0-0 | 73-21-17 | D05832J | | | | | | | D05832J | | | 46 | 275-299 |
| FR5 | | | | 0-0 | 73-21-17 | D05315J | | | | | | | D05315J | | | 10 | 275-299 |
| FRA | | | | 0-0 | 73-21-11 | D05832J | | | | | | | D05832J | | | 29 | 050-099 |
| FRB | | | | 0-0 | 73-21-14 | D06582J | | | 13 | | | | D06582J | | | | FH 050-099 |
| FRC | | | | 0-0 | 73-21-11 | D06582J | | | | | | | D06582J | | | 16 | 050-099 |
| FRC | | | | 0-0 | 73-21-14 | D06582J | | | | | | | D06582J | | | 13 | 150-199 |
| FRC | | | | 0-0 | 73-21-14 | D06582J | | | 13 | | | | D06582J | | | | FC 277-299 |
| FRD | | | | 0-0 | 78-36-11 | D05306J | | | | | | | D05306J | | | 10 | 050-099 |
| FRF | | | | 0-0 | 73-21-17 | D05832J | | | | | | | D05832J | | | 46 | 050-099 |
| FRJ | | | | 0-0 | 73-21-14 | D06582J | | | 9 | | | | D06582J | | | | FJ 050-099 |
| FRL | | | | 0-0 | 73-21-17 | D05315J | | | | | | | D05315J | | | 10 | 050-099 |
| FRS | | | | 0-0 | 73-21-14 | D06582J | | | | | | | D06582J | | | 9 | 150-199, 275-299 |
| FRT | | | | 0-0 | 78-36-11 | D05306J | | | 10 | | | | D05306J | | | | \$ FT 150-199 |
| FRT | | | | 0-0 | 78-36-11 | D05306J | | | 10 | | | | D05306J | | | | FT 275-299 |
| GRD | | | | 0-0 | 78-34-11 | D05300J | | | | | | | D05300J | | | 56 | ALL |
| GRH | | | | 0-0 | 78-34-11 | D05306J | | | 47 | | | | D05306J | | | | HH ALL |
| GRK | | | | 0-0 | 78-34-21 | TB0080X | | | C015 | | BJ | | TB0080X | | | | HK ALL |
| GRM | | | | 0-0 | 78-34-11 | D05308J | | | | | | | D05308J | | | 33 | ALL |
| GRP | | | | 0-0 | 78-34-21 | D05832J | | | | | | | D05832J | | | 31 | ALL |
| GRU | | | | 0-0 | 78-34-11 | D04709J | | | | | | | D04709J | | | 21 | ALL |
| PA1 | | | | 0-0 | 99-99-99 | D10160 | | | G2 | | | | D10160 | | | G3 | ALL |

WIRE LIST

D280T132

91-21-11

Section W0170

Page 66 End

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0180 | 286T0180 | | | P36-R2-INTEGRATION | | | | | | | | | | | |
| 001 | 24 | | PK | | 4-0 | 21-53-12 | D05348J | | | | TB0220X | A009 | BJ | | ALL |
| 002 | 24 | | PK | | 4-0 | 24-22-22 | D04716J | | | | TB0220Y | A020 | BJ | | ALL |
| 003 | 24 | | PK | | 4-0 | 21-53-12 | D05348J | | | | TB0220X | C009 | BJ | | ALL |
| 004 | 24 | | PK | | 4-0 | 21-53-12 | D05348J | | | | TB0220X | D009 | BJ | | ALL |
| 005 | 24 | | PK | | 4-0 | 21-53-12 | D05348J | | | | TB0220X | A010 | BJ | | ALL |
| 006 | 24 | | PK | | 4-0 | 21-53-12 | D05348J | | | | TB0220X | B010 | BJ | | ALL |
| 007 | 24 | | PK | | 4-0 | 21-53-12 | D05348J | | | | TB0220X | B009 | BJ | | ALL |
| 010 | 24 | | PK | | 4-0 | 21-58-16 | D05348J | | | | TB0272Z | 16 | BJ | | ALL |
| 012 | 24 | | PK | | 4-0 | 21-58-16 | D05348J | | | | TB0220X | A014 | BJ | | ALL |
| 013 | 24 | | PK | | 4-0 | 21-58-16 | D05348J | | | | TB0220X | B014 | BJ | | ALL |
| 014 | 16 | | PA | | 5-0 | 33-45-11 | D05348J | | 23 | FL | TB0302F | A010 | 2 | | ALL |
| 015 | 16 | | PA | | 5-0 | 33-45-11 | D05348J | | 24 | FL | TB0302F | C010 | 2 | | ALL |
| 016 | 24 | | PK | | 4-0 | 21-58-16 | D05348J | | 3 | | TB0220Y | C011 | BJ | | ALL |
| 017 | 22 | | PQ | E | 4-0 | 27-09-12 | D04716J | | 25 | | TB0220X | B005 | BJ | | ALL |
| 017Z | | | | E | 0-0 | 27-09-12 | D04716J | | DED | | TB0220X | DED | | | ALL |
| 021 | 20 | | PA | | 5-0 | 33-42-11 | D04716J | | 8 | | K00161 | X2 | C | | ALL |
| 022 | 20 | | PA | | 5-0 | 33-42-11 | D04716J | | 7 | | K00161 | X1 | C | | ALL |
| 026 | 24 | | PK | | 4-0 | 36-23-21 | D04716J | | 11 | | TB0218X | A002 | BJ | | ALL |
| 027 | 24 | | PK | | 4-0 | 36-23-21 | D04716J | | 12 | | TB0220X | C005 | BJ | | ALL |
| 029 | 24 | | PK | | 4-0 | 21-53-12 | D05348J | | 18 | | TB0222Z | 3 | BJ | | ALL |
| 031 | 24 | | PK | | 4-0 | 21-53-12 | D05192J | | 1 | | TB0222Z | 4 | BJ | | ALL |
| 034 | 18 | | PA | | 5-0 | 33-31-21 | D05348J | | 21 | DL | TB0302F | C009 | 2 | | ALL |
| 035 | 24 | | PK | | 4-0 | 32-31-11 | D05348J | | 1 | | TB0220X | C004 | BJ | | ALL |
| 037 | 22 | | PA | | 4-0 | 52-11-12 | D05348J | | 27 | | TB0220Y | C020 | BJ | | 050-099, 150-199 |
| 037 | 20 | | PA | | 4-0 | 52-11-12 | D05348J | | 27 | | TB0220Y | C020 | BJ | | 275-299 |
| 038 | 22 | | PA | | 4-0 | 52-11-12 | D05126J | | 8 | | TB0220X | B016 | BJ | | 050-099, 150-199 |
| 038 | 20 | | PA | | 4-0 | 52-11-12 | D05126J | | 8 | | TB0220X | B016 | BJ | | 275-299 |
| 054 | 18 | | PA | | 4-0 | 28-41-12 | D05348J | | 2 | DL | TB0216F | A007 | 2 | | ALL |
| 055 | 22 | | PA | | 4-0 | 28-41-12 | D04716J | | 13 | | TB0272G | 8 | 2 | | ALL |
| 056 | 22 | | PA | | 4-0 | 28-41-22 | D04716J | | 1 | | TB0272G | 8 | 2 | | ALL |
| 057 | 22 | | PA | | 4-0 | 28-41-23 | D04716J | | 2 | | TB0272G | 8 | 2 | | ALL |
| 058 | 24 | | PK | | 5-0 | 23-31-13 | D05126J | | 9 | | TB0302X | D005 | BJ | | ALL |
| 061 | 24 | | PK | | 4-0 | 21-44-21 | D05348J | | 30 | | TB0220X | C014 | BJ | | ALL |
| 075 | 24 | | PK | | 4-0 | 33-16-14 | D05348J | | 25 | | TB0220X | D016 | BJ | | ALL |
| 084 | 24 | | PK | | 4-0 | 21-53-12 | D05348J | | 16 | | TB0220X | B015 | BJ | | ALL |
| 098 | 18 | | PA | | 4-0 | 32-71-11 | D05192J | | 4 | DL | TB0272G | 30 | 2 | | 150-199, 275-299 |
| 102 | 20 | | PA | | 4-0 | 25-31-11 | D04716J | | 29 | | D10318 | D3 | | | 050-099, 150-199, 275-278 |
| 102 | 18 | | PA | | 4-0 | 25-31-11 | D04716J | | 29 | DL | D10318 | D3 | | | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0180
Page 1
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0180 | 286T0180 | | | P36-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 103 | 20 | | PA | | 4-0 | 25-31-11 | D05348J | | 40 | | D10318 | | D2 | | 050-099, 150-199, 275-278 |
| 103 | 18 | | PA | | 4-0 | 25-31-11 | D05348J | | 40 | DL | D10318 | | D2 | | 280-299 |
| 104 | 18 | | PQ | B | 4-0 | 25-31-21 | D10318 | | B2 | | TB0272F | | C012 | 2 | ALL |
| 104Z | | | | B | 0-0 | 25-31-21 | D10318 | | DED | | TB0272F | | DED | | ALL |
| 105 | 18 | | PQ | D | 4-0 | 25-31-21 | D10318 | | B3 | | TB0272F | | A012 | 2 | ALL |
| 105Z | | | | D | 0-0 | 25-31-21 | D10318 | | DED | | TB0272F | | DED | | ALL |
| 106 | 18 | | PQ | AB | 4-0 | 25-31-31 | D10318 | | C3 | | TB0272F | | C027 | 2 | 277-299 |
| 106Z | | | | AB | 0-0 | 25-31-31 | D10318 | | DED | | TB0272F | | DED | | 277-299 |
| 107 | 18 | | PQ | AC | 4-0 | 25-31-31 | D10318 | | C2 | | TB0272F | | A027 | 2 | 277-299 |
| 107Z | | | | AC | 0-0 | 25-31-31 | D10318 | | DED | | TB0272F | | DED | | 277-299 |
| 108 | 24 | | PK | | 4-0 | 21-58-12 | D05348J | | 28 | | TB0220X | | A006 | BJ | ALL |
| 109 | 24 | | PK | | 4-0 | 21-58-12 | D05348J | | 26 | | TB0220X | | B006 | BJ | ALL |
| 113 | 24 | | PK | | 4-0 | 24-51-71 | D10314 | | 2 | | TB0272X | | B002 | BJ | ALL |
| 114 | 24 | | PK | | 2-0 | 24-51-71 | D10314 | | 6 | | D10316 | | 7 | | ALL |
| 116 | 24 | | PK | | 4-0 | 24-51-71 | D10314 | | 7 | | TB0216Y | | C002 | BJ | ALL |
| 117 | 20 | | PA | | 2-0 | 24-51-71 | D10314 | | 3 | | GD0003 | | D.. | 2 | ALL |
| 118 | 24 | | PK | | 4-0 | 24-51-71 | D10314 | | 8 | | TB0216Y | | A005 | BJ | ALL |
| 119 | 24 | | PK | | 4-0 | 24-51-71 | D10314 | | 5 | | TB0272X | | A001 | BJ | ALL |
| 11A | 24 | | PK | | 5-0 | 21-43-11 | D05192J | | 3 | | TB0302X | | C003 | BJ | ALL |
| 120 | 24 | | PK | | 2-0 | 24-51-71 | D10316 | | 2 | | D10318 | | X1 | | ALL |
| 121 | 20 | | PA | | 2-0 | 24-51-71 | D10316 | | 6 | | GD0003 | | D.. | 2 | ALL |
| 122 | 20 | | PQ | F | 5-0 | 27-32-31 | D04716J | | 6 | | TB0216X | | A003 | BJ | ALL |
| 122Z | | | | F | 0-0 | 27-32-31 | D04716J | | DED | | TB0216X | | DED | | ALL |
| 123 | 24 | | PK | | 4-0 | 24-51-71 | D10316 | | 3 | | TB0218Y | | A008 | BJ | ALL |
| 124 | 24 | | PK | | 4-0 | 24-51-71 | D10316 | | 5 | | TB0216Y | | A005 | BJ | ALL |
| 125 | 24 | | PK | | 4-0 | 24-51-71 | D10316 | | 1 | | TB0218Y | | A008 | BJ | ALL |
| 126 | 24 | | PK | | 5-0 | 27-38-11 | D05348J | | 38 | | TB0302X | | D003 | BJ | ALL |
| 127 | 24 | | PK | | 4-0 | 24-51-71 | D10318 | | X2 | | TB0218Y | | A008 | BJ | ALL |
| 128 | 24 | | PK | | 5-0 | 21-44-21 | D05348J | | 29 | | TB0216Y | | C005 | BJ | 050-099, 150-199 |
| 128 | 24 | | PK | | 5-0 | 21-44-21 | D05348J | | 29 | | TB0218X | | B001 | BJ | 275-299 |
| 130 | 24 | | PK | | 5-0 | 21-44-21 | D05348J | | 31 | | TB0302X | | C002 | BJ | ALL |
| 132 | 24 | | PK | | 5-0 | 21-43-11 | D05192J | | 2 | | TB0302Y | | A011 | BJ | ALL |
| 135 | 24 | | PK | | 8-0 | 31-31-26 | D05126J | | 7 | | TB0078Y | | A001 | BJ | ALL |
| 137 | 18 | | PA | | 4-0 | SPARE | D10318 | | A2 | | D05348J | | 41 | DL | 280-299 |
| 138 | 18 | | PA | | 4-0 | SPARE | D10318 | | A3 | | D04716J | | 30 | DL | 280-299 |
| 139 | 24 | | PK | | 5-0 | 30-21-11 | D04716J | | 4 | | TB0216X | | A004 | BJ | 050-099 |
| 139 | 24 | | PK | | 4-0 | 30-21-11 | D04716J | | 4 | | TB0216X | | A004 | BJ | 150-199 |
| 145 | 18 | | PA | | 6-0 | 38-32-11 | D05348J | | 22 | DL | TB0076F | | A015 | 2 | 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|----------|---------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0180 | 286T0180 | | | P36-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 146 | 18 | PA | | 4-0 | 38-32-11 | D04716J | | 4 | DL | | TB0218F | A020 | 2 | | 275-276 |
| 154 | 22 | PQ | AD | 5-0 | 29-11-12 | D04716J | | 31 | | | TB0220X | D007 | BJ | | ALL |
| 154Z | | | AD | 0-0 | 29-11-12 | D04716J | | | DED | | TB0220X | DED | | | ALL |
| 160 | 20 | PQ | HA | 8-0 | 78-34-21 | D04716J | | 5 | | | TB0080X | A015 | BJ | | ALL |
| 160Z | | | HA | 0-0 | 78-34-21 | D04716J | | | | HJ | TB0080X | | | HK | ALL |
| 161 | 20 | PQ | HB | 8-0 | 78-34-21 | D04716J | | 27 | | | TB0080X | B015 | BJ | | ALL |
| 161Z | | | HB | 0-0 | 78-34-21 | D04716J | | | | HJ | TB0080X | | | HK | ALL |
| 181 | 22 | PA | | 5-0 | 21-66-41 | TB0318D | | C007 | 2 | | D05348J | 36 | | | 150, 152-157 |
| 201B | 24 | PL | A | 4-0 | 21-61-51 | D04716J | | 9 | | | TB0218X | C001 | BJ | | 050-099 |
| 201B | 24 | PL | A | 5-0 | 21-61-51 | D04716J | | 9 | | | TB0218X | C001 | BJ | | 150-199, 275-299 |
| 201R | 24 | PL | A | 0-0 | 21-61-51 | D04716J | | 10 | | | TB0218X | D001 | BJ | | ALL |
| 202B | 24 | PW | C | 4-0 | 32-42-11 | D04716J | | 21 | | | TB0272X | C001 | BJ | | 050-099 |
| 202B | 24 | PW | C | 5-0 | 32-42-11 | D04716J | | 21 | | | TB0272X | C001 | BJ | | 150-199, 275-299 |
| 202R | 24 | PW | C | 0-0 | 32-42-11 | D04716J | | 20 | | | TB0272X | D001 | BJ | | ALL |
| 202Z | | | C | 0-0 | 32-42-11 | D04716J | | 22 | | | TB0272X | A002 | BJ | | ALL |
| 70A | 22 | PA | | 6-0 | 21-45-22 | D04716J | | 3 | | | TB0076X | A002 | BJ | | ALL |
| GRJ | | | | 0-0 | 78-34-21 | D04716J | | | | HJ | D04716J | 17 | | | ALL |
| GRK | | | | 0-0 | 78-34-21 | TB0080X | | C015 | BJ | | TB0080X | | | HK | ALL |
| W0181 | 286T0181 | | | E1-6 L,SHELF | | | | | | | | | | | |
| 003 | 22 | PA | | 4-4 | 34-21-31 | D04757P | | 3 | | | D00369B | D01 | | | ALL |
| 004 | 22 | PA | | 4-4 | 34-21-31 | D04757P | | 4 | | | D00369B | D02 | | | ALL |
| 005 | 22 | PA | | 4-4 | 34-21-31 | D04757P | | 5 | | | D00369B | D03 | | | ALL |
| 006 | 24 | PV | AF | 4-0 | 34-21-31 | D04293P | | 1 | | | D00369C | 1 | | | ALL |
| 006Z | | | AF | 0-0 | 34-21-31 | D04293P | | | DED | | D00369C | DED | | | ALL |
| 007 | 20 | PA | | 2-7 | 34-21-31 | GDX0006 | | A.. | 2 | | D00369C | 5 | | | ALL |
| 008 | 16 | PA | | 2-7 | 34-21-31 | GDX0006 | | D.. | 2 | | D00369C | 8 | | | ALL |
| 009 | 16 | PA | | 2-7 | 34-21-31 | GDX0006 | | S.. | 2 | | D00369C | 11 | | | ALL |
| 010 | 24 | PK | | 1-0 | 34-21-31 | SM00001 | | | W | | D00369B | A02 | | | 275-299 |
| 012 | 24 | PK | | 4-4 | 34-21-31 | D04757P | | 12 | | | D00369B | F01 | | | ALL |
| 013 | 24 | PK | | 4-4 | 34-21-31 | D04757P | | 13 | | | D00369B | F02 | | | ALL |
| 014 | 22 | PA | | 4-4 | 34-21-31 | D04757P | | 14 | | | D00369B | E13 | | | ALL |
| 015 | 22 | PA | | 4-7 | 34-21-31 | D04757P | | 15 | | | TB0161G | 35 | 2 | | ALL |
| 016 | 22 | PA | | 4-7 | 34-21-31 | D04757P | | 16 | | | TB0161G | 36 | 2 | | ALL |
| 017 | 22 | PA | | 4-7 | 34-21-31 | D04757P | | 17 | | | TB0161G | 37 | 2 | | ALL |
| 018 | 22 | PA | | 3-1 | 34-21-31 | TB0161G | | 35 | 2 | | D00369B | E12 | | | ALL |
| 019 | 22 | PA | | 3-1 | 34-21-31 | TB0161G | | 36 | 2 | | D00369B | E11 | | | ALL |
| 020 | 22 | PA | | 3-1 | 34-21-31 | TB0161G | | 37 | 2 | | D00369B | E10 | | | ALL |
| 021 | 12 | PA | | 4-0 | 34-21-31 | D00369C | | 7 | | | D04773P | 1 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0180
Page 3
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0181 | 286T0181 | | | E1-6 L,SHELF (continued) | | | | | | | | | | | | | |
| 022 | 22 | | PA | | 3-1 | 34-21-31 | D00369B | E09 | | | | | TB0161G | 38 | 2 | | ALL |
| 036 | 24 | | PK | | 4-0 | 34-21-31 | D00369B | J13 | | | | | D04969P | 20 | | | ALL |
| 038 | 22 | | PA | | 3-10 | 22-21-11 | D04969P | 25 | | | | | TB0161G | 38 | 2 | | ALL |
| 048 | 22 | | PA | | 4-4 | 33-16-17 | D04757P | 8 | | | | | D00369B | E08 | | | ALL |
| 053 | 22 | | PA | | 3-10 | 34-21-31 | TB0161G | 35 | 2 | | | | D04969P | 32 | | | ALL |
| 054 | 22 | | PA | | 3-10 | 34-21-31 | TB0161G | 36 | 2 | | | | D04969P | 34 | | | ALL |
| 055 | 22 | | PA | | 3-10 | 34-21-31 | TB0161G | 37 | 2 | | | | D04969P | 33 | | | ALL |
| 080 | 24 | | PK | | 1-0 | 34-21-31 | D00369B | A01 | | | | | SM00001 | | W | | ALL |
| 081 | 24 | | PK | | 1-0 | 34-21-31 | D00369B | A02 | | | | | SM00001 | | W | | 050-099, 150-199 |
| 082 | 24 | | PK | | 1-0 | 34-21-31 | D00369B | K09 | | | | | SM00001 | | W | | 050-099, 150-199 |
| 083 | 24 | | PK | | 1-0 | 34-21-31 | D00369B | K03 | | | | | SM00001 | | W | | 150-199, 275-299 |
| 101 | 24 | | PK | | 3-9 | 34-22-37 | D04969P | 13 | | | | | TB0161G | 44 | 2 | | ALL |
| 102 | 24 | | PK | | 3-9 | 34-22-17 | D04969P | 16 | | | | | TB0161G | 44 | 2 | | ALL |
| 201B | 24 | | PW | IA | 4-8 | 34-21-31 | D04757P | 20 | | | | | TB0161G | 40 | 2 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-21-31 | D04757P | 19 | | | | | TB0161G | 39 | 2 | | ALL |
| 201Z | | | | IA | 0-0 | 34-21-31 | D04757P | 21 | | | | | GDY0005 | S.. | 2 | | ALL |
| 202B | 24 | | PW | IB | 4-5 | 34-21-31 | D04757P | 23 | | | | | TB0161H | 33 | 2 | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-21-31 | D04757P | 24 | | | | | TB0161H | 31 | 2 | | ALL |
| 202Z | | | | IB | 0-0 | 34-21-31 | D04757P | 22 | | | | | GDY0004 | S.. | 2 | | ALL |
| 203B | 24 | | PW | IC | 3-2 | 34-21-31 | TB0161G | 40 | 2 | | | | D00369B | C06 | | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 34-21-31 | TB0161G | 39 | 2 | | | | D00369B | C05 | | | ALL |
| 203Z | | | | IC | 0-0 | 34-21-31 | GDY0005 | S.. | 2 | | | | D00369B | DED | | | ALL |
| 204B | 24 | | PW | ID | 3-1 | 34-21-31 | TB0161H | 33 | 2 | | | | D00369B | C11 | | | ALL |
| 204R | 24 | | PW | ID | 0-0 | 34-21-31 | TB0161H | 31 | 2 | | | | D00369B | C10 | | | ALL |
| 204Z | | | | ID | 0-0 | 34-21-31 | GDY0004 | S.. | 2 | | | | D00369B | DED | | | ALL |
| 205B | 24 | | PW | IE | 3-5 | 34-21-31 | D00369B | J11 | | | | | TB0161G | 20 | 2 | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 34-21-31 | D00369B | J10 | | | | | TB0161G | 19 | 2 | | ALL |
| 205Z | | | | IE | 0-0 | 34-21-31 | D00369B | DED | | | | | GDY0003 | S.. | 2 | | ALL |
| 207B | 24 | | PW | IG | 3-3 | 34-21-31 | D00369B | A09 | | | | | TB0161G | 22 | 2 | | ALL |
| 207R | 24 | | PW | IG | 0-0 | 34-21-31 | D00369B | A08 | | | | | TB0161G | 21 | 2 | | ALL |
| 207Z | | | | IG | 0-0 | 34-21-31 | D00369B | DED | | | | | GDY0003 | S.. | 2 | | ALL |
| 208B | 24 | | PW | IH | 3-3 | 34-21-31 | D00369B | A14 | | | | | TB0161G | 25 | 2 | | ALL |
| 208R | 24 | | PW | IH | 0-0 | 34-21-31 | D00369B | A13 | | | | | TB0161G | 24 | 2 | | ALL |
| 208Z | | | | IH | 0-0 | 34-21-31 | D00369B | DED | | | | | GDY0003 | S.. | 2 | | ALL |
| 209 | 20 | | UA | | 1-6 | 34-22-38 | GDX0006 | S.. | 2 | | | | D00369B | | | II | ALL |
| 209B | 24 | | PW | II | 4-0 | 34-22-38 | D04969P | 5 | | | | | D00369B | E06 | | | ALL |
| 209R | 24 | | PW | II | 0-0 | 34-22-38 | D04969P | 4 | | | | | D00369B | E05 | | | ALL |
| 209Z | | | | II | 0-0 | 34-22-38 | D04969P | 6 | | | | | D00369B | | | II | ALL |
| 210B | 24 | | PW | IJ | 3-11 | 34-22-81 | D04969P | 40 | | | | | TB0161H | 33 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0181 | 286T0181 | | | E1-6 L,SHELF (continued) | | | | | | | | | | | | |
| 210R | 24 | PW | IJ | | 0-0 | 34-22-81 | D04969P | | 39 | | | TB0161H | 31 | 2 | | ALL |
| 210Z | | | IJ | | 0-0 | 34-22-81 | D04969P | | 41 | | | GDY0004 | S.. | 2 | | ALL |
| 211B | 24 | PW | IK | | 3-1 | 34-21-31 | D00369B | | G08 | | | TB0161G | 30 | 2 | | ALL |
| 211R | 24 | PW | IK | | 0-0 | 34-21-31 | D00369B | | G07 | | | TB0161G | 29 | 2 | | ALL |
| 211Z | | | IK | | 0-0 | 34-21-31 | D00369B | | DED | | | GDY0004 | S.. | 2 | | ALL |
| 212B | 24 | PW | IL | | 4-1 | 34-22-18 | D04969P | | 11 | | | TB0161G | 30 | 2 | | ALL |
| 212R | 24 | PW | IL | | 0-0 | 34-22-18 | D04969P | | 10 | | | TB0161G | 29 | 2 | | ALL |
| 212Z | | | IL | | 0-0 | 34-22-18 | D04969P | | 12 | | | GDY0004 | S.. | 2 | | ALL |
| 213B | 24 | PW | IM | | 4-8 | 34-61-12 | TB0161G | | 16 | 2 | | D05153P | 7 | | | ALL |
| 213R | 24 | PW | IM | | 0-0 | 34-61-12 | TB0161G | | 15 | 2 | | D05153P | 6 | | | ALL |
| 213Z | | | IM | | 0-0 | 34-61-12 | GDY0003 | | S.. | 2 | | D05153P | 8 | | | ALL |
| 214B | 24 | PW | IN | | 3-11 | 34-43-11 | D04969P | | 8 | | | TB0161H | 33 | 2 | | ALL |
| 214R | 24 | PW | IN | | 0-0 | 34-43-11 | D04969P | | 7 | | | TB0161H | 31 | 2 | | ALL |
| 214Z | | | IN | | 0-0 | 34-43-11 | D04969P | | 9 | | | GDY0004 | S.. | 2 | | ALL |
| 215B | 24 | PW | IO | | 3-2 | 34-22-28 | D05629P | | 2 | | | TB0161G | 30 | 2 | | ALL |
| 215R | 24 | PW | IO | | 0-0 | 34-22-28 | D05629P | | 1 | | | TB0161G | 29 | 2 | | ALL |
| 215Z | | | IO | | 0-0 | 34-22-28 | D05629P | | 3 | | | GDY0004 | S.. | 2 | | ALL |
| 216B | 24 | PW | IP | | 3-4 | 31-35-13 | D04969P | | 27 | | | D05153P | 14 | | | ALL |
| 216R | 24 | PW | IP | | 0-0 | 31-35-13 | D04969P | | 26 | | | D05153P | 15 | | | ALL |
| 216Z | | | IP | | 0-0 | 31-35-13 | D04969P | | 28 | | | D05153P | 18 | | | ALL |
| 217B | 24 | PW | IQ | | 3-11 | 32-42-11 | D04969P | | 37 | | | TB0161H | 33 | 2 | | ALL |
| 217R | 24 | PW | IQ | | 0-0 | 32-42-11 | D04969P | | 36 | | | TB0161H | 31 | 2 | | ALL |
| 217Z | | | IQ | | 0-0 | 32-42-11 | D04969P | | 38 | | | GDY0004 | S.. | 2 | | ALL |
| 219B | 24 | PW | IS | | 3-1 | 34-21-31 | D00369B | | K05 | | | TB0161G | 27 | 2 | | ALL |
| 219R | 24 | PW | IS | | 0-0 | 34-21-31 | D00369B | | K04 | | | TB0161G | 26 | 2 | | ALL |
| 219Z | | | IS | | 0-0 | 34-21-31 | D00369B | | DED | | | GDY0004 | S.. | 2 | | ALL |
| 220B | 24 | PW | IT | | 3-11 | 22-21-11 | D04969P | | 24 | | | TB0161H | 33 | 2 | | ALL |
| 220R | 24 | PW | IT | | 0-0 | 22-21-11 | D04969P | | 23 | | | TB0161H | 31 | 2 | | ALL |
| 220Z | | | IT | | 0-0 | 22-21-11 | D04969P | | 22 | | | GDY0004 | S.. | 2 | | ALL |
| 221B | 24 | PW | IU | | 3-7 | 34-21-31 | TB0161G | | 16 | 2 | | TB0161H | 33 | 2 | | ALL |
| 221R | 24 | PW | IU | | 0-0 | 34-21-31 | TB0161G | | 15 | 2 | | TB0161H | 31 | 2 | | ALL |
| 221Z | | | IU | | 0-0 | 34-21-31 | GDY0003 | | S.. | 2 | | TB0161H | DED | | | ALL |
| W0182 | 286T0182 | | | P36-L1-INTEGRATION | | | | | | | | | | | | |
| 002 | 16 | PA | | | 5-0 | 38-13-11 | D05100J | | 7 | | | TB0222G | 6 | 2 | | ALL |
| 003 | 24 | PK | | | 3-0 | 21-53-11 | D03504 | | X1 | | | TB0076Z | 12 | BJ | | 050-099 |
| 003 | 24 | PK | | | 3-0 | 21-53-11 | D03504 | | X1 | | | TB0076Y | A005 | BJ | | 150-199, 275-299 |
| 004 | 24 | PK | | | 3-0 | 21-53-11 | D03504 | | X2 | | | TB0076Y | C004 | BJ | | ALL |
| 005 | 24 | PK | | | 3-0 | 21-53-12 | D03506 | | B3 | | | D03546 | A1 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0180
Page 5
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0182 | 286T0182 | | | P36-L1-INTEGRATION (continued) | | | | | | | | | | | | | |
| 006 | 24 | | PK | 3-0 | 21-53-12 | D03506 | | A3 | | | | | D03490 | A1 | | | ALL |
| 007 | 24 | | PK | 3-0 | 21-53-11 | D03506 | | X1 | | | | | TB0076Z | 12 | BJ | | 050-099 |
| 007 | 24 | | PK | 3-0 | 21-53-11 | D03506 | | X1 | | | | | TB0076Y | A005 | BJ | | 150-199, 275-299 |
| 008 | 24 | | PK | 3-0 | 21-53-11 | D03506 | | X2 | | | | | TB0076Y | C004 | BJ | | ALL |
| 009 | 24 | | PK | 3-0 | 21-53-12 | D03482 | | A1 | | | | | D03504 | A3 | | | ALL |
| 010 | 24 | | PK | 5-0 | 21-53-12 | D03482 | | A2 | | | | | TB0222Z | 4 | BJ | | ALL |
| 011 | 24 | | PK | 5-0 | 21-53-12 | D03482 | | X1 | | | | | TB0222Z | 3 | BJ | | ALL |
| 012 | 24 | | PK | 5-0 | 21-53-12 | D03482 | | X2 | | | | | TB0220X | A009 | BJ | | ALL |
| 013 | 24 | | PK | 3-0 | 21-53-12 | D03484 | | A1 | | | | | D03504 | B3 | | | ALL |
| 014 | 24 | | PK | 5-0 | 21-53-12 | D03484 | | A2 | | | | | TB0222Z | 4 | BJ | | ALL |
| 015 | 24 | | PK | 5-0 | 21-53-12 | D03484 | | X1 | | | | | TB0222Z | 3 | BJ | | ALL |
| 016 | 24 | | PK | 5-0 | 21-53-12 | D03484 | | X2 | | | | | TB0220X | C009 | BJ | | ALL |
| 017 | 24 | | PK | 3-0 | 21-53-12 | D03486 | | A1 | | | | | D03504 | C3 | | | ALL |
| 018 | 24 | | PK | 5-0 | 21-53-12 | D03486 | | A2 | | | | | TB0222Z | 4 | BJ | | ALL |
| 019 | 24 | | PK | 5-0 | 21-53-12 | D03486 | | X1 | | | | | TB0222Z | 3 | BJ | | ALL |
| 020 | 24 | | PK | 5-0 | 21-53-12 | D03486 | | X2 | | | | | TB0220X | B010 | BJ | | ALL |
| 021 | 24 | | PK | 3-0 | 21-53-12 | D03488 | | A1 | | | | | D03504 | D3 | | | ALL |
| 022 | 24 | | PK | 5-0 | 21-53-12 | D03488 | | A2 | | | | | TB0222Z | 4 | BJ | | ALL |
| 023 | 24 | | PK | 5-0 | 21-53-12 | D03488 | | X1 | | | | | TB0222Z | 3 | BJ | | ALL |
| 024 | 24 | | PK | 5-0 | 21-53-12 | D03488 | | X2 | | | | | TB0220X | B009 | BJ | | ALL |
| 025 | 24 | | PK | 5-0 | 21-53-12 | D03490 | | A2 | | | | | TB0222Z | 4 | BJ | | ALL |
| 026 | 24 | | PK | 5-0 | 21-53-12 | D03490 | | X1 | | | | | TB0222Z | 3 | BJ | | ALL |
| 027 | 24 | | PK | 5-0 | 21-53-12 | D03490 | | X2 | | | | | TB0220X | D009 | BJ | | ALL |
| 028 | 24 | | PK | 5-0 | 21-53-12 | D03546 | | A2 | | | | | TB0222Z | 4 | BJ | | ALL |
| 029 | 24 | | PK | 5-0 | 21-53-12 | D03546 | | X1 | | | | | TB0222Z | 3 | BJ | | ALL |
| 030 | 24 | | PK | 5-0 | 21-53-12 | D03546 | | X2 | | | | | TB0220X | A010 | BJ | | ALL |
| 034 | 24 | | PK | 5-0 | SPARE | D05952J | | CAP | Y | | | | TB0222X | CAP | Y | | 051-099, 150-154 |
| 034 | 24 | | PK | 5-0 | 21-44-21 | D05952J | | 7 | | | | | TB0222X | A017 | BJ | | 275-276 |
| 035 | 24 | | PK | 5-0 | SPARE | D05952J | | CAP | Y | | | | TB0222X | CAP | Y | | 051-099, 150-154 |
| 035 | 24 | | PK | 5-0 | 21-44-21 | D05952J | | 8 | | | | | TB0222X | B017 | BJ | | 275-276 |
| 037 | 12 | | PA | 6-0 | 21-25-11 | K00415 | | C1 | E | | | | D04920J | 4 | | | ALL |
| 039 | 18 | | PA | 5-0 | 21-25-11 | D04920J | | 1 | | | | | TB0302F | A009 | 2 | | ALL |
| 040 | 14 | | PA | 6-4 | 21-26-11 | D04920J | | 8 | | | | | K00347 | A2 | E | | ALL |
| 041 | 18 | | PA | 4-0 | 38-32-12 | D05100J | | 5 | | | | | TB0302G | 19 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 041 | 18 | | PA | 2-0 | 38-32-12 | D05100J | | 5 | | | | | D05952J | 1 | DK | | 156 |
| 043 | 24 | | PK | 5-0 | 21-43-11 | TB0222X | | B010 | BJ | | | | D03568 | A2 | | | ALL |
| 044 | 24 | | PK | 3-0 | 21-43-11 | D04288J | | 11 | | | | | D04918J | 27 | | | 050-099 |
| 044 | 24 | | PK | 5-0 | 21-43-11 | D04288J | | 11 | | | | | D04918J | 27 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0182 | 286T0182 | | | P36-L1-INTEGRATION (continued) | | | | | | | | | | | |
| 045 | 22 | PA | | | 6-0 | 21-44-11 | TB0302X | A002 | BJ | | D04918J | 14 | | | ALL |
| 046 | 24 | PK | | | 5-0 | 21-44-11 | TB0222X | B009 | BJ | | D03566 | B2 | | | ALL |
| 047 | 24 | PK | | | 5-0 | 21-44-11 | D04288J | | 18 | | D03566 | X1 | | | ALL |
| 049 | 24 | PK | | | 5-0 | 21-53-11 | D04288J | | 2 | | D03506 | B1 | | | ALL |
| 050 | 24 | PK | | | 5-0 | 21-53-11 | D04288J | | 3 | | D03506 | A1 | | | ALL |
| 051 | 24 | PK | | | 5-0 | 21-53-11 | D04288J | | 4 | | D03504 | D1 | | | ALL |
| 052 | 24 | PK | | | 5-0 | 21-53-11 | D04288J | | 5 | | D03504 | C1 | | | ALL |
| 053 | 24 | PK | | | 5-0 | 21-53-11 | D04288J | | 6 | | D03504 | B1 | | | ALL |
| 054 | 24 | PK | | | 5-0 | 21-53-11 | D04288J | | 7 | | D03504 | A1 | | | ALL |
| 055 | 24 | PK | | | 6-0 | 21-53-11 | D04288J | | 24 | | TB0076X | C001 | BJ | | ALL |
| 057 | 24 | PK | | | 7-0 | 21-43-11 | TB0302X | B003 | BJ | | D03568 | A3 | | | ALL |
| 058 | 24 | PK | | | 7-0 | 21-43-11 | TB0302X | C001 | BJ | | D03568 | A1 | | | ALL |
| 059 | 24 | PK | | | 6-0 | 21-43-11 | D04918J | | 29 | | D03568 | X2 | | | ALL |
| 060 | 24 | PK | | | 6-0 | 21-44-11 | D04918J | | 15 | | D03566 | B3 | | | ALL |
| 061 | 24 | PK | | | 6-0 | 21-44-11 | D04918J | | 16 | | D03566 | B1 | | | ALL |
| 062 | 24 | PK | | | 6-0 | 21-44-11 | D04918J | | 17 | | D03566 | X2 | | | ALL |
| 063 | 24 | PK | | | 6-0 | 21-53-11 | D04918J | | 5 | | D03504 | A2 | | | ALL |
| 064 | 24 | PK | | | 6-0 | 21-53-11 | D04918J | | 22 | | D03504 | B2 | | | ALL |
| 065 | 24 | PK | | | 6-0 | 21-53-11 | D04918J | | 7 | | D03504 | C2 | | | ALL |
| 066 | 24 | PK | | | 6-0 | 21-53-11 | D04918J | | 26 | | D03504 | D2 | | | ALL |
| 067 | 24 | PK | | | 6-0 | 21-53-11 | D04918J | | 9 | | D03506 | A2 | | | ALL |
| 068 | 24 | PK | | | 6-0 | 21-53-11 | D04918J | | 32 | | D03506 | B2 | | | ALL |
| 070 | 24 | PK | | | 5-0 | 21-26-11 | D04918J | | 18 | | TB0302X | B001 | BJ | | ALL |
| 071 | 12 | PA | | | 5-0 | 21-25-11 | D04920J | | 2 | | K00415 | A1 | E | | ALL |
| 072 | 12 | PA | | | 5-0 | 21-25-11 | D04920J | | 3 | | K00415 | B1 | E | | ALL |
| 074 | 14 | PA | | | 5-0 | 21-26-11 | D04920J | | 9 | | K00347 | B2 | E | | ALL |
| 075 | 14 | PA | | | 5-0 | 21-26-11 | D04920J | | 10 | | K00347 | C2 | E | | ALL |
| 097 | 20 | PA | | | 3-0 | 21-31-11 | D04918J | | 19 | | D04288J | 28 | | | ALL |
| 098 | 18 | PA | | | 5-0 | 33-31-21 | D04920J | | 11 | | TB0302F | C009 | 2 | | ALL |
| 105 | 24 | PK | | | 5-0 | 21-44-21 | D00582 | | B2 | | TB0222X | C001 | BJ | | ALL |
| 106 | 24 | PK | | | 6-0 | 21-44-21 | D00582 | | X1 | | TB0216Y | C005 | BJ | | 050-099, 150-199 |
| 106 | 24 | PK | | | 6-0 | 21-44-21 | D00582 | | X1 | | TB0218X | B001 | BJ | | 275-299 |
| 107 | 24 | PK | | | 5-0 | 21-44-21 | D00582 | | X2 | | TB0220X | C014 | BJ | | ALL |
| 108 | 22 | PA | | | 5-0 | 21-44-21 | TB0302X | A003 | BJ | | D04918J | 25 | | | ALL |
| 109 | 22 | PA | | | 6-0 | 21-44-21 | D00582 | | B3 | | D04918J | 23 | | | ALL |
| 110 | 22 | PA | | | 6-0 | 21-44-21 | D00582 | | B1 | | D04918J | 24 | | | ALL |
| 111 | 20 | PA | | | 5-0 | 30-41-11 | D04288J | | 12 | | TB0222X | D009 | BJ | | ALL |
| 112 | 20 | PA | | | 5-0 | 30-41-11 | D04288J | | 13 | | TB0222X | A010 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0180
 Page 7
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0182 | 286T0182 | | | P36-L1-INTEGRATION (continued) | | | | | | | | | | | | | |
| 118 | 18 | | PA | 4-0 | 38-32-11 | D05456J | | 3 | | | | | TB0222H | 11 | 2 | | 050-099, 150-155, 162-165 |
| 118 | 18 | | PA | 10-0 | 38-32-11 | D05456J | | 3 | | | | | D12382 | B3 | | | 275-276 |
| 119 | 22 | | PA | 7-0 | 38-32-11 | K00172 | | X2 | C | | | | TB0222H | 11 | 2 | | 050-099, 275-299 |
| 119 | 20 | | PA | 7-0 | 38-32-11 | K00172 | | X2 | C | | | | TB0222H | 11 | 2 | | 150-199 |
| 120 | 12 | | PA | 6-0 | 38-32-11 | K00172 | | A2 | E | | | | D05952J | 20 | | | ALL |
| 121 | 12 | | PA | 6-0 | 38-32-11 | K00172 | | B2 | E | | | | D05952J | 22 | | | ALL |
| 122 | 12 | | PA | 6-0 | 38-32-11 | K00172 | | C2 | E | | | | D05952J | 24 | | | ALL |
| 123 | 22 | | PA | 6-0 | 38-32-11 | K00172 | | X1 | C | | | | D05952J | 2 | | | 050-099, 275-299 |
| 123 | 20 | | PA | 6-0 | 38-32-11 | K00172 | | X1 | C | | | | D05952J | 2 | | | 150-199 |
| 124 | 22 | | PA | 5-0 | 38-32-11 | D05952J | | 6 | | | | | TB0222H | 11 | 2 | | 050-099, 155, 165, 275-276 |
| 124 | 20 | | PA | 5-0 | 38-32-11 | D05952J | | 6 | | | | | TB0222H | 11 | 2 | | 150-154, 156-164, 166-199 |
| 124 | 18 | | PA | 5-0 | 38-32-11 | D05952J | | 6 | DK | | | | TB0222H | 11 | 2 | | 277-299 |
| 125 | 18 | | PA | 6-0 | 38-32-12 | D01356 | | B2 | | | | | TB0222H | 11 | 2 | | 050 |
| 125 | 18 | | PA | 6-0 | 38-32-11 | D01356 | | B2 | | | | | TB0222H | 11 | 2 | | 051-099 |
| 125 | 18 | | PA | 5-0 | 38-32-12 | D01356 | | B2 | | | | | TB0222H | 11 | 2 | | 150-155, 162-165, 275-276 |
| 125 | 18 | | PA | 5-0 | 38-32-11 | D21234 | | B2 | | | | | TB0222H | 11 | 2 | | 156-157, 166-199, 277-299 |
| 126 | 18 | | PA | 6-0 | 38-32-12 | D01356 | | A2 | | | | | TB0222H | 11 | 2 | | 050-099 |
| 126 | 18 | | PA | 5-0 | 38-32-12 | D01356 | | A2 | | | | | TB0222H | 11 | 2 | | 150-155, 162-165, 275-276 |
| 126 | 20 | | PA | 10-0 | 38-32-11 | D21232 | | A2 | | | | | D05456J | 10 | | | 156-157, 166-199, 277-299 |
| 127 | 18 | | PA | 8-0 | 38-32-12 | D01356 | | B1 | | | | | TB0302G | 19 | 2 | | 050-099 |
| 127 | 18 | | PA | 7-0 | 38-32-12 | D01356 | | B1 | | | | | TB0302G | 19 | 2 | | 150-155, 162-165, 275-276 |
| 127 | 18 | | PA | 7-0 | 38-32-11 | D21234 | | B1 | | | | | TB0302G | 19 | 2 | * | 156-157, 166-199, 277-299 |
| 128 | 18 | | PA | 8-0 | 38-32-12 | D01356 | | A1 | | | | | TB0302G | 19 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 128 | 22 | | PA | 10-0 | 38-32-11 | D21232 | | A1 | | | | | TB0302F | C020 | 2 | | 156-157, 166-199, 277-299 |
| 129 | 22 | | PA | 6-0 | 38-32-12 | D01356 | | X1 | | | | | D05952J | 1 | | | 050-099, 165, 275-276 |
| 129 | 20 | | PA | 6-0 | 38-32-12 | D01356 | | X1 | | | | | D05952J | 1 | | | 150-155, 162-164 |
| 129 | 20 | | PA | 8-0 | 38-32-11 | D21234 | | X1 | | | | | TB0302G | 19 | 2 | * | 156, 166 |
| 129 | 22 | | PA | 8-0 | 38-32-11 | D21234 | | X1 | | | | | TB0302G | 19 | 2 | * | 157, 167-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 8

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0182 | 286T0182 | | | P36-L1-INTEGRATION (continued) | | | | | | | | | | | |
| 130 | 20 | | PA | | 3-0 | 38-32-12 | D01356 | | X2 | | GDX0007 | D.. | 2 | | 050-099, 150-154, 275-276 |
| 130 | 20 | | PA | | 3-0 | 38-32-11 | D01356 | | X2 | | GDX0007 | D.. | 2 | | 155, 162-165 |
| 130 | 20 | | PA | | 3-0 | 38-32-11 | D21234 | | X2 | | GDX0007 | D.. | 2 | | 156-157, 166-199, 277-299 |
| 135 | 18 | | PA | | 5-0 | 21-24-11 | D05100J | | 4 | | TB0272F | A019 | 2 | | 050-099 |
| 135 | 18 | | UA | | 8-0 | 21-24-11 | TB0272F | A019 | 2 | | D05100J | | 4 | | 150-199 |
| 136 | 18 | | PA | | 5-0 | 21-24-11 | D05100J | | 6 | | TB0272F | C019 | 2 | | 050-099 |
| 136 | 18 | | UA | | 8-0 | 21-24-11 | TB0272F | C019 | 2 | | D05100J | | 6 | | 150-199 |
| 137 | 18 | | PA | | 5-4 | 21-24-11 | D05100J | | 8 | | TB0302F | C031 | 2 | | 050-099 |
| 137 | 18 | | PA | | 5-4 | 21-24-11 | D05100J | | 8 | | TB0302F | C030 | 2 | | 150-199 |
| 138 | 16 | | PA | | 6-0 | 28-22-11 | K00190 | | A1 | D | D05892J | | 1 | | ALL |
| 139 | 16 | | PA | | 6-0 | 28-22-11 | K00190 | | B1 | D | D05892J | | 2 | | ALL |
| 140 | 16 | | PA | | 6-0 | 28-22-11 | K00190 | | C1 | D | D05892J | | 3 | | ALL |
| 141 | 16 | | PA | | 6-0 | 28-22-11 | K00187 | | A1 | D | D04918J | | 1 | | ALL |
| 142 | 16 | | PA | | 6-0 | 28-22-11 | K00187 | | B1 | D | D04918J | | 2 | | ALL |
| 143 | 16 | | PA | | 6-0 | 28-22-11 | K00187 | | C1 | D | D04918J | | 4 | | ALL |
| 144 | 12 | | PA | | 6-0 | 28-22-12 | K00329 | | A1 | D | D04920J | | 5 | | ALL |
| 145 | 12 | | PA | | 6-0 | 28-22-12 | K00329 | | B1 | D | D04920J | | 6 | | ALL |
| 146 | 12 | | PA | | 6-0 | 28-22-12 | K00329 | | C1 | D | D04920J | | 7 | | ALL |
| 150 | 18 | | PA | | 8-0 | 38-32-14 | D11930 | | A3 | | D05952J | | 9 | DK | 050-099, 150-154 |
| 151 | 18 | | PA | | 8-0 | 38-32-14 | D11930 | | A1 | | D05952J | | 10 | DK | 050-099, 150-199, 277-299 |
| 151 | 18 | | PA | | 9-0 | 38-32-14 | D12394 | | A1 | | D05952J | | 10 | DK | 275-276 |
| 152 | 20 | | PA | | 8-0 | 38-32-14 | D11930 | | X2 | | K00172 | | X1 | C | 050-099, 150-199, 277-299 |
| 152 | 20 | | PA | | 10-0 | 38-32-14 | D12394 | | X2 | | D05952J | | 9 | | 275-276 |
| 153 | 18 | | PA | | 9-0 | 38-32-14 | D11930 | | A2 | | TB0302G | | 32 | 2 | 050-099, 150-199 |
| 153 | 18 | | PA | | 10-0 | 38-32-14 | D12394 | | A2 | | GDX0003 | | D.. | 2 | 275-276 |
| 153 | 18 | | PA | | 9-0 | 38-32-14 | D11930 | | A2 | | TB0318G | | 22 | 2 | 277-299 |
| 154 | 18 | | PA | | 4-0 | 38-32-14 | D05456J | | 6 | DK | TB0302G | | 32 | 2 | 050-099, 150-199 |
| 154 | 18 | | PA | | 4-0 | 38-32-14 | D05456J | | 6 | DK | TB0318G | | 22 | 2 | 277-278 |
| 154 | 18 | | PA | | 4-0 | 38-32-14 | D05456J | | 6 | | TB0318G | | 22 | 2 | 280-299 |
| 155 | 20 | | PA | | 9-0 | 38-32-14 | D11930 | | X1 | | TB0302G | | 32 | 2 | 050-099, 150-199 |
| 155 | 20 | | PA | | 4-0 | 38-32-14 | D12394 | | X1 | | TB0222H | | 11 | 2 | 275-276 |
| 155 | 20 | | PA | | 9-0 | 38-32-14 | D11930 | | X1 | | TB0318G | | 22 | 2 | 277-299 |
| 156 | 20 | | PA | | 5-0 | 38-32-11 | D05952J | | 11 | | TB0222X | C010 | BJ | | 050-099 |
| 156 | 20 | | PA | | 6-0 | 38-32-11 | D05952J | | 11 | | TB0222X | C010 | BJ | | 155-199, 277-299 |
| 156 | 20 | | PA | | 6-0 | SPARE | D05952J | | 11 | | TB0222X | C010 | BJ | | 276 |

WIRE LIST
D280T132

91-21-11
Section W0180
Page 9
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0182 | 286T0182 | | | P36-L1-INTEGRATION (continued) | | | | | | | | | | | | |
| 161 | 12 | | PA | 6-0 | 28-31-21 | C00375 | A2 | D | | K02093 | A2 | D | | 050-099, 162-164, 276 | | |
| 161 | 12 | | PA | 9-0 | 28-31-21 | C00375 | A2 | D | | D04918J | 10 | | | 155-157, 165-199, 277-299 | | |
| 162 | 12 | | PA | 6-0 | 28-31-21 | C00375 | B2 | D | | K02093 | B2 | D | | 050-099, 162-164, 276 | | |
| 162 | 12 | | PA | 9-0 | 28-31-21 | C00375 | B2 | D | | D04918J | 8 | | | 155-157, 165-199, 277-299 | | |
| 163 | 12 | | PA | 6-0 | 28-31-21 | C00375 | C2 | D | | K02093 | C2 | D | | 050-099, 162-164, 276 | | |
| 163 | 12 | | PA | 9-0 | 28-31-21 | C00375 | C2 | D | | D04918J | 6 | | | 155-157, 165-199, 277-299 | | |
| 164 | 12 | | PA | 6-0 | 28-31-21 | K02093 | A1 | D | | D04918J | 10 | | | 050-099 | | |
| 164 | 12 | | PA | 6-0 | 28-31-21 | D04918J | 10 | | | K02093 | A1 | D | | 162-164, 276 | | |
| 165 | 12 | | PA | 6-0 | 28-31-21 | K02093 | B1 | D | | D04918J | 8 | | | 050-099 | | |
| 165 | 12 | | PA | 6-0 | 28-31-21 | D04918J | 8 | | | K02093 | B1 | D | | 162-164, 276 | | |
| 166 | 12 | | PA | 6-0 | 28-31-21 | K02093 | C1 | D | | D04918J | 6 | | | 050-099 | | |
| 166 | 12 | | PA | 6-0 | 28-31-21 | D04918J | 6 | | | K02093 | C1 | D | | 162-164, 276 | | |
| 168 | 18 | | PA | 9-0 | 38-32-11 | D12382 | X1 | | | TB0302G | 32 | 2 | | 275-276 | | |
| 169 | 18 | | PA | 9-0 | 38-32-11 | D12382 | B1 | | | TB0302G | 32 | 2 | | 275-276 | | |
| 170 | 20 | | PA | 2-0 | 38-32-11 | D12382 | X2 | | | GD0003 | D.. | 2 | | 275-276 | | |
| 171 | 18 | | PA | 6-0 | 38-32-11 | D12382 | B2 | | | TB0222H | 11 | 2 | | 275-276 | | |
| 172 | 18 | | PA | 12-0 | 38-32-11 | D12382 | A3 | | | TB0076F | A015 | 2 | | 275-276 | | |
| 173 | 18 | | PA | 12-0 | 38-32-11 | D12382 | A1 | | | TB0076F | C015 | 2 | | 275-276 | | |
| 174 | 18 | | PA | 6-0 | 38-32-11 | D12382 | A2 | | | TB0218F | A020 | 2 | | 275-276 | | |
| 196 | 12 | | PA | 10-0 | 21-73-11 | C01129 | A2 | D | | D05952J | 14 | | | 275-299 | | |
| 197 | 12 | | PA | 10-0 | 21-73-11 | C01129 | B2 | D | | D05952J | 16 | | | 275-299 | | |
| 198 | 12 | | PA | 10-0 | 21-73-11 | C01129 | C2 | D | | D05952J | 18 | | | 275-299 | | |
| 200 | 12 | | PA | 5-0 | 38-32-11 | K00172 | A1 | E | | TB5076 | 5 | C | | 050-099 | | |
| 200 | 12 | | PA | 3-0 | 38-32-11 | K00172 | A1 | E | | TB5076 | 5 | C | | 150-199, 275-299 | | |
| 201 | 12 | | PA | 5-0 | 38-32-11 | K00172 | B1 | E | | TB5076 | 6 | C | | 050-099 | | |
| 201 | 12 | | PA | 3-0 | 38-32-11 | K00172 | B1 | E | | TB5076 | 6 | C | | 150-199, 275-299 | | |
| 201B | 24 | | PW | A | 3-0 | 21-31-11 | D04918J | 13 | | D04288J | 21 | | | ALL | | |
| 201R | 24 | | PW | A | 0-0 | 21-31-11 | D04918J | 12 | | D04288J | 20 | | | ALL | | |
| 201Z | | | | A | 0-0 | 21-31-11 | D04918J | 11 | | D04288J | 22 | | | ALL | | |
| 202 | 12 | | PA | 5-0 | 38-32-11 | K00172 | C1 | E | | TB5076 | 7 | C | | 050-099 | | |
| 202 | 12 | | PA | 3-0 | 38-32-11 | K00172 | C1 | E | | TB5076 | 7 | C | | 150-199, 275-299 | | |
| 203B | 12 | | PB | C | 7-0 | 30-41-11 | D04288J | 19 | | TB5076 | 12 | C | | ALL | | |
| 203R | 12 | | PB | C | 0-0 | 30-41-11 | D04288J | 23 | | TB5076 | 13 | C | | ALL | | |
| 206B | 20 | | PB | D | 3-0 | 21-31-11 | D04288J | 25 | | D04918J | 20 | | | ALL | | |
| 206R | 20 | | PB | D | 0-0 | 21-31-11 | D04288J | 26 | | D04918J | 21 | | | ALL | | |
| 505 | 22 | | PA | 3-0 | 21-51-11 | TB0076X | A001 | BJ | | D03506 | D1 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 10

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0182 | 286T0182 | | | P36-L1-INTEGRATION (continued) | | | | | | | | | | | |
| 506 | 22 | | PA | | 3-0 | 21-51-11 | TB0076X | B001 | BJ | | D03506 | D2 | | | ALL |
| 510 | 24 | | PK | | 7-0 | 21-43-11 | D03568 | X1 | | | TB0302Y | A011 | BJ | | 050-099 |
| 510 | 24 | | PK | | 5-0 | 21-43-11 | D03568 | X1 | | | TB0302Y | A011 | BJ | | 150-199, 275-299 |
| 512 | 24 | | PK | | 5-0 | 21-44-21 | D05952J | 5 | | | TB0302X | D002 | BJ | | ALL |
| 550 | 24 | | PK | | 4-0 | 21-43-11 | D04288J | 8 | | | TB0318X | D036 | BJ | | 050-099 |
| 550 | 24 | | PK | | 5-0 | 21-43-11 | D04288J | 8 | | | TB0318X | D036 | BJ | | 150-199, 275-299 |
| 70A | 20 | | PA | | 6-0 | 25-42-11 | D05100J | 1 | | | TB0220X | B004 | BJ | | 050-099, 275-299 |
| 70A | 20 | | PA | | 6-0 | 25-42-11 | TB0220X | B004 | BJ | | D05100J | 1 | | | 150-199 |
| 70B | 22 | | PA | | 10-0 | 38-32-11 | D05456J | 9 | | | D21232 | A3 | | | 156-157, 166-199, 277-299 |
| 70C | 22 | | PA | | 10-0 | 38-32-11 | D21232 | X1 | | | TB0302F | C020 | 2 | | 156-157, 166-199, 277-299 |
| 70F | 18 | | PA | | 6-0 | 38-32-11 | D05456J | 3 | | | D21234 | B3 | | | 156-157, 166-199, 277-299 |
| 70H | 20 | | PA | | 10-0 | 38-32-11 | D21232 | X2 | | | GDX0015 | D.. | 2 | | 156-157, 166-199, 277-299 |
| W0183 | 286T0183 | | | E2-6 SHELF | | | | | | | | | | | |
| 068 | 24 | | PK | | 3-0 | 32-45-11 | D06802P | 1 | | | D13366A | A01 | | | 275-299 |
| 069 | 24 | | PK | | 3-0 | 32-45-11 | D06802P | 2 | | | D13366B | A13 | | | 275-299 |
| 070 | 22 | | PA | | 3-0 | 32-45-11 | D13366A | B01 | | | GDX0002 | D.. | 2 | | 275-299 |
| 071 | 22 | | PA | | 3-0 | 32-45-11 | D13366A | D01 | | | GDX0002 | S.. | 2 | | 275-299 |
| 075 | 22 | | PA | | 3-0 | 32-45-11 | D13366A | D03 | | | GDX0002 | S.. | 2 | | 275-299 |
| 234 | 20 | | UA | | 3-0 | 32-45-11 | D13366B | REF | | J1 | GDX0002 | S.. | 2 | | 275-299 |
| 234B | 24 | | PW | J1 | 4-0 | 32-45-11 | D06804P | 2 | | | D13366B | B05 | | | 275-299 |
| 234R | 24 | | PW | J1 | 0-0 | 32-45-11 | D06804P | 1 | | | D13366B | A05 | | | 275-299 |
| 234Z | | | | J1 | 0-0 | 32-45-11 | D06804P | 3 | | | D13366B | REF | | J1 | 275-299 |
| 235B | 24 | | PW | JJ | 3-0 | 32-45-12 | D13366B | B04 | | | D06802P | 4 | | | 275-299 |
| 235R | 24 | | PW | JJ | 0-0 | 32-45-12 | D13366B | A04 | | | D06802P | 3 | | | 275-299 |
| 235Z | | | | JJ | 0-0 | 32-45-12 | D13366B | C04 | | | D06802P | 5 | | | 275-299 |
| 236B | 24 | | PW | JK | 3-0 | 32-45-12 | D13366B | B03 | | | D06802P | 7 | | | 275-299 |
| 236R | 24 | | PW | JK | 0-0 | 32-45-12 | D13366B | A03 | | | D06802P | 6 | | | 275-299 |
| 236Z | | | | JK | 0-0 | 32-45-12 | D13366B | C03 | | | D06802P | 8 | | | 275-299 |
| 237B | 24 | | PW | JL | 3-0 | 32-45-13 | D13366A | B02 | | | D06806P | 1 | | | 275-299 |
| 237R | 24 | | PW | JL | 0-0 | 32-45-13 | D13366A | A02 | | | D06806P | 2 | | | 275-299 |
| 237Z | | | | JL | 0-0 | 32-45-13 | D13366A | C02 | | | D06806P | 3 | | | 275-299 |
| 238B | 24 | | PW | JM | 3-0 | 32-45-13 | D13366A | B03 | | | D06806P | 4 | | | 275-299 |
| 238R | 24 | | PW | JM | 0-0 | 32-45-13 | D13366A | A03 | | | D06806P | 5 | | | 275-299 |
| 238Z | | | | JM | 0-0 | 32-45-13 | D13366A | C03 | | | D06806P | 6 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0183 | 286T0183 | | | E2-6 SHELF (continued) | | | | | | | | | | | | |
| 239B | 24 | PW | JN | 3-0 | 32-45-13 | D13366A | B06 | | | | D06806P | 7 | | | 275-299 | |
| 239R | 24 | PW | JN | 0-0 | 32-45-13 | D13366A | A06 | | | | D06806P | 8 | | | 275-299 | |
| 239Z | | | JN | 0-0 | 32-45-13 | D13366A | C06 | | | | D06806P | 9 | | | 275-299 | |
| 240B | 24 | PW | JO | 3-0 | 32-45-13 | D13366A | B07 | | | | D06806P | 10 | | | 275-299 | |
| 240R | 24 | PW | JO | 0-0 | 32-45-13 | D13366A | A07 | | | | D06806P | 11 | | | 275-299 | |
| 240Z | | | JO | 0-0 | 32-45-13 | D13366A | C07 | | | | D06806P | 12 | | | 275-299 | |
| 241B | 24 | PW | JP | 4-0 | 32-45-14 | D13366A | B04 | | | | D06808P | 1 | | | 275-299 | |
| 241R | 24 | PW | JP | 0-0 | 32-45-14 | D13366A | A04 | | | | D06808P | 2 | | | 275-299 | |
| 241Z | | | JP | 0-0 | 32-45-14 | D13366A | C04 | | | | D06808P | 3 | | | 275-299 | |
| 242B | 24 | PW | JQ | 4-0 | 32-45-14 | D13366A | B05 | | | | D06808P | 4 | | | 275-299 | |
| 242R | 24 | PW | JQ | 0-0 | 32-45-14 | D13366A | A05 | | | | D06808P | 5 | | | 275-299 | |
| 242Z | | | JQ | 0-0 | 32-45-14 | D13366A | C05 | | | | D06808P | 6 | | | 275-299 | |
| 243B | 24 | PW | JR | 4-0 | 32-45-14 | D13366A | B08 | | | | D06808P | 7 | | | 275-299 | |
| 243R | 24 | PW | JR | 0-0 | 32-45-14 | D13366A | A08 | | | | D06808P | 8 | | | 275-299 | |
| 243Z | | | JR | 0-0 | 32-45-14 | D13366A | C08 | | | | D06808P | 9 | | | 275-299 | |
| 244B | 24 | PW | JS | 4-0 | 32-45-14 | D13366A | B09 | | | | D06808P | 10 | | | 275-299 | |
| 244R | 24 | PW | JS | 0-0 | 32-45-14 | D13366A | A09 | | | | D06808P | 11 | | | 275-299 | |
| 244Z | | | JS | 0-0 | 32-45-14 | D13366A | C09 | | | | D06808P | 12 | | | 275-299 | |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION | | | | | | | | | | | | |
| 002 | 22 | PA | | 5-0 | 31-31-11 | D03526 | B2 | | | | TB0218X | A011 | BJ | | 050-099, 150-199 | |
| 002 | 22 | PA | | 6-0 | 31-31-11 | D03526 | B2 | | | | TB0218X | A011 | BJ | | 275-299 | |
| 003 | 20 | PA | | 3-0 | 27-58-21 | D00928 | 6 | | | | GDX0009 | S.. | 2 | | ALL | |
| 004 | 24 | PK | | 7-0 | 27-58-21 | D00928 | 4 | | | | D08026J | 14 | | | ALL | |
| 005 | 22 | PA | | 7-0 | 27-58-21 | D00928 | 5 | | | | D08026J | 17 | | | ALL | |
| 006 | 22 | PA | | 5-0 | 31-31-11 | D03526 | B1 | | | | TB0218X | B011 | BJ | | ALL | |
| 007 | 20 | PA | | 3-0 | 27-58-21 | D00928 | 1 | | | | GDX0009 | A.. | 2 | | ALL | |
| 011 | 24 | PK | | 5-0 | 36-23-21 | D03626 | A2 | | | | TB0220X | C005 | BJ | | ALL | |
| 012 | 20 | PA | | 3-0 | 36-23-21 | D03626 | A1 | | | | GDX0002 | D.. | 2 | | ALL | |
| 01P | 24 | PV | FA | 6-0 | 76-11-11 | D13824 | X1 | | | | TB0216Z | 14 | BJ | | 050-099 | |
| 01P | 24 | PV | FA | 4-0 | 76-11-11 | D13824 | X1 | | | | TB0216Z | 14 | BJ | | 150-154, 275-276 | |
| 01P | 24 | PV | FA | 4-0 | 76-11-11 | D13824 | X1 | | | | TB0080Z | 4 | BJ | | 155-199, 277-299 | |
| 01PZ | | | FA | 0-0 | 76-11-11 | D13824 | DED | | | | TB0216Z | DED | | | 050-099, 150-154, 275-276 | |
| 01PZ | | | FA | 0-0 | 76-11-11 | D13824 | DED | | | | TB0080Z | DED | | | 155-199, 277-299 | |
| 01R | 20 | PQ | FB | 8-0 | 76-11-11 | D13824 | X2 | | | | GDX0009 | D.. | 2 | | 050-099, 150-154, 275-276 | |
| 01R | 20 | PQ | FB | 8-0 | 76-11-11 | D13824 | X2 | | | | GDX0009 | D.. | 2 | | 155-199, 277-299 | |
| 01RZ | | | FB | 0-0 | 76-11-11 | D13824 | DED | | | | GDX0009 | DED | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 12

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | |
| 01U | 18 | PQ | FC | | 8-0 | 24-11-11 | D13824 | | A3 | | D06310J | 23 | DL | | 050-099 |
| 01U | 18 | PQ | FC | | 6-0 | 24-11-11 | D13824 | | A3 | | D06310J | 23 | DL | | 150-199, 275-299 |
| 01UZ | | | FC | | 0-0 | 24-11-11 | D13824 | | DED | | D06310J | DED | | | ALL |
| 01V | 18 | PQ | FD | | 8-0 | 24-11-11 | D13824 | | A2 | | D06310J | 24 | DL | | 050-099 |
| 01V | 18 | PQ | FD | | 6-0 | 24-11-11 | D13824 | | A2 | | D06310J | 24 | DL | | 150-199, 275-299 |
| 01VZ | | | FD | | 0-0 | 24-11-11 | D13824 | | DED | | D06310J | DED | | | ALL |
| 025 | 24 | PK | | | 4-0 | 21-58-12 | D06310J | | 11 | | TB0218Y | A013 | BJ | | ALL |
| 026 | 24 | PK | | | 5-0 | 21-58-12 | D03578 | | X1 | | TB0252Z | 6 | BJ | | 050-099 |
| 026 | 24 | PK | | | 8-0 | 21-58-12 | D03578 | | X1 | | TB0252Z | 6 | BJ | | 150-199, 275-299 |
| 029 | 24 | PK | | | 8-0 | 21-58-12 | D03578 | | X2 | | TB0250D | A005 | 2 | | ALL |
| 02H | 20 | PQ | AI | | 4-0 | 78-34-11 | D06310J | | 8 | | TB0302Y | C017 | BJ | | 050-099 |
| 02H | 20 | PQ | AI | | 6-0 | 78-34-11 | D06310J | | 8 | | TB0302Y | C017 | BJ | | 150-199, 275-299 |
| 02HZ | | | AI | | 0-0 | 78-34-11 | D06310J | | DED | | TB0302Y | DED | | | ALL |
| 02K | 24 | PV | QE | | 8-4 | 28-22-12 | D04856J | | 13 | | TB0218X | B012 | BJ | | 150-199 |
| 02KZ | | | QE | | 0-0 | 28-22-12 | D04856J | | DED | | TB0218X | DED | | | 150-199 |
| 030 | 24 | PK | | | 8-0 | 21-58-12 | D03578 | | A1 | | TB0250X | B003 | BJ | | ALL |
| 032 | 24 | PK | | | 6-0 | 21-58-12 | D03578 | | A2 | | TB0272Y | C023 | BJ | | 050-099 |
| 032 | 24 | PK | | | 8-0 | 21-58-12 | D03578 | | A2 | | TB0272Y | C023 | BJ | | 150-199, 275-299 |
| 034 | 24 | PV | G | | 4-0 | 32-09-11 | D08026J | | 47 | | TB0216Z | 13 | BJ | | ALL |
| 034Z | | | G | | 0-0 | 32-09-11 | D08026J | | DED | | TB0216Z | DED | | | ALL |
| 054 | 24 | PK | | | 5-0 | 21-58-12 | TB0218Y | | C018 | BJ | D06310J | 12 | | | 050-099 |
| 054 | 24 | PK | | | 4-0 | 21-58-12 | TB0218Y | | C018 | BJ | D06310J | 12 | | | 150-199, 275-299 |
| 058 | 24 | PV | BB | | 3-0 | 21-58-14 | TB0220X | | C010 | BJ | TB0218Y | A010 | BJ | | 050-099 |
| 058 | 24 | PV | BB | | 4-0 | 21-58-14 | TB0220X | | C010 | BJ | TB0218Y | A010 | BJ | | 150-199, 275-299 |
| 058Z | | | BB | | 0-0 | 21-58-14 | TB0218Y | | DED | | TB0220X | DED | | | ALL |
| 062 | 22 | PA | | | 4-0 | 21-58-16 | D10422 | | A2 | | TB0078Y | A013 | BJ | | ALL |
| 063 | 22 | PA | | | 4-0 | 21-58-16 | D10422 | | A1 | | TB0078Y | C014 | BJ | | ALL |
| 064 | 24 | PK | | | 4-0 | 21-58-16 | D10422 | | X1 | | TB0078Z | 10 | BJ | | ALL |
| 065 | 24 | PK | | | 5-0 | 21-58-16 | D10422 | | X2 | | TB0220Y | C011 | BJ | | ALL |
| 066 | 22 | PA | | | 6-0 | 21-58-16 | D04992J | | 47 | | D10462 | C2 | | | 050-099 |
| 066 | 22 | PA | | | 8-0 | 21-58-16 | D04992J | | 47 | | D10462 | C2 | | | 150-199, 275-299 |
| 067 | 22 | PA | | | 3-0 | 21-58-16 | D10418 | | A2 | | TB0216Y | A016 | BJ | | ALL |
| 068 | 24 | PK | | | 5-0 | 21-58-16 | D10418 | | B2 | | D06310J | 14 | | | ALL |
| 069 | 20 | PA | | | 3-0 | 21-58-16 | D10418 | | X2 | | GDY0012 | D.. | 2 | | ALL |
| 070 | 18 | PA | | | 2-0 | 32-44-11 | D08026J | | 8 | DL | D04992J | 10 | DK | | ALL |
| 071 | 18 | PA | | | 2-0 | 32-44-11 | D08026J | | 9 | DL | D04992J | 8 | DK | | ALL |
| 072 | 22 | PA | | | 5-0 | 21-58-16 | D10418 | | A1 | | D05654J | 6 | | | ALL |
| 073 | 24 | PK | | | 5-0 | 32-44-11 | D03620 | | 13 | | D04992J | 14 | | | ALL |
| 074 | 24 | PK | | | 5-0 | 21-58-16 | D10418 | | B1 | | TB0222X | C013 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 13

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 075 | 20 | | PA | 4-0 | 32-44-11 | D03620 | | | | 2 | | | TB0218Y | C006 | BJ | | 050-099 |
| 075 | 20 | | PA | 6-0 | 32-44-11 | D03620 | | | | 2 | | | TB0218Y | C006 | BJ | | 150-199, 275-299 |
| 076 | 20 | | PA | 3-0 | 32-44-11 | D03620 | | | | 12 | | | GDX0001 | D.. | 2 | | ALL |
| 077 | 24 | | PK | 2-0 | 21-58-16 | D10418 | | | | X1 | | | D10416 | A1 | | | ALL |
| 078 | 24 | | PK | 8-0 | 21-58-16 | TB0252Z | | | | 7 | BJ | | D04992J | 46 | | | ALL |
| 079 | 24 | | PK | 5-0 | 32-44-11 | D03620 | | | | 6 | | | D04992J | 7 | | | ALL |
| 080 | 24 | | PK | 4-0 | 21-58-16 | D10416 | | | | A2 | | | TB0078Z | 10 | BJ | | 050-099 |
| 080 | 24 | | PK | 3-0 | 21-58-16 | D10416 | | | | A2 | | | TB0078Z | 10 | BJ | | 150-199, 275-299 |
| 081 | 22 | | PA | 4-0 | 32-44-11 | TB0218Y | | | | C006 | BJ | | D04992J | 12 | | | ALL |
| 082 | 22 | | PA | 5-0 | 32-44-11 | D04992J | | | | 4 | | | D03620 | 1 | | | ALL |
| 083 | 24 | | PK | 4-0 | 21-58-16 | D10416 | | | | X1 | | | TB0078Z | 10 | BJ | | ALL |
| 084 | 24 | | PK | 4-0 | 21-58-16 | D10416 | | | | X2 | | | TB0272Z | 16 | BJ | | ALL |
| 085 | 24 | | PK | 4-0 | 28-41-11 | D04942J | | | | 24 | | | TB0272Y | A005 | BJ | | ALL |
| 087 | 22 | | PA | 4-0 | 21-58-16 | D06310J | | | | 16 | | | TB0216Y | A016 | BJ | | ALL |
| 08A | 22 | | PA | 6-0 | 73-21-19 | TB0220X | | | | A016 | BJ | | D10550 | 13 | | | 275-299 |
| 08B | 22 | | PA | 6-0 | 73-21-19 | TB0218Y | | | | C007 | % | | D10550 | 1 | | | 275-299 |
| 08C | 20 | | PA | 3-0 | 73-21-19 | GDX0002 | | | | D.. | 2 | | D10550 | 12 | | | 275-299 |
| 08D | 22 | | PA | 6-0 | 73-21-19 | D10550 | | | | 6 | | | TB0258D | C006 | 2 | | 275-299 |
| 095 | 18 | | PA | 11-0 | 28-21-11 | D04942J | | | | 42 | | | C00094 | 1 | D | | 050-099, 150-156, 162-166, 275-276 |
| 095 | 18 | | PA | 10-0 | 28-21-11 | D04942J | | | | 44 | DK | | C00094 | 1 | D | | 157, 167-199, 277-299 |
| 097 | 22 | | PA | 6-0 | 28-21-11 | D04856J | | | | 15 | | | D03594 | C3 | | | ALL |
| 09B | 20 | | PA | 3-0 | SPARE | D03526 | | | | D2 | | | GDX0001 | CAP | Y | | 150-156, 162-166 |
| 100 | 18 | | PA | 3-0 | 28-21-11 | D03594 | | | | C1 | | | TB0078G | 16 | 2 | | ALL |
| 101 | 22 | | PA | 3-0 | 28-21-11 | D03594 | | | | X1 | | | TB0078G | 16 | 2 | | ALL |
| 102 | 22 | | PA | 6-0 | 28-21-11 | D03594 | | | | X2 | | | D04942J | 8 | | | ALL |
| 104 | 24 | | PK | 4-0 | 28-41-11 | D04992J | | | | 20 | | | TB0218Y | A018 | BJ | | ALL |
| 105 | 18 | | PA | 3-0 | 28-21-11 | D03594 | | | | C2 | | | TB0078G | 15 | 2 | | ALL |
| 106 | 18 | | PA | 3-0 | 28-21-11 | D03538 | | | | A2 | | | TB0078G | 15 | 2 | | ALL |
| 107 | 18 | | PA | 3-0 | 28-21-11 | D03538 | | | | X1 | | | TB0078G | 15 | 2 | | ALL |
| 109 | 22 | | PA | 3-0 | 28-21-11 | D03538 | | | | X2 | | | TB0078Y | C003 | BJ | | ALL |
| 10B | 22 | | PQ | AA | 5-0 | 28-31-12 | D04856J | | | 4 | | | TB0302D | A037 | 2 | | 050-099 |
| 10B | 22 | | PQ | AF | 5-0 | 28-31-12 | D04856J | | | 4 | | | TB0302D | A037 | 2 | | 155-199, 276-299 |
| 10BZ | | | | AA | 0-0 | 28-31-12 | D04856J | | | DED | | | TB0302D | DED | | | 050-099 |
| 10BZ | | | | AF | 0-0 | 28-31-12 | D04856J | | | DED | | | TB0302D | DED | | | 155-199, 276-299 |
| 10D | 22 | | PQ | AG | 15-0 | 28-42-12 | D08026J | | | 5 | | | TB0218Y | A005 | BJ | | 050-099, 155-199, 276-299 |
| 10DZ | | | | AG | 0-0 | 28-42-12 | D08026J | | | DED | | | TB0218Y | DED | | | 050-099, 155-199, 276-299 |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 14

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|----------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | |
| 10E | 22 | PQ | AD | 4-0 | 28-42-13 | D04856J | | 8 | | | TB0218Y | C009 | BJ | | 050-099 |
| 10E | 22 | PQ | AH | 4-0 | 28-42-13 | D04856J | | 8 | | | TB0218Y | C009 | BJ | | 155-199, 276-299 |
| 10EZ | | | AD | 0-0 | 28-42-13 | D04856J | | DED | | | TB0218Y | DED | | | 050-099 |
| 10EZ | | | AH | 0-0 | 28-42-13 | D04856J | | DED | | | TB0218Y | DED | | | 155-199, 276-299 |
| 111 | 18 | PA | | 5-0 | 28-21-11 | D03538 | | A1 | | | TB0272H | 10 | 2 | | ALL |
| 112 | 18 | PA | | 11-0 | 28-21-11 | C00094 | | 1 | D | | TB0272H | 10 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 112 | 18 | PA | | 10-0 | 28-21-11 | C00094 | | 1 | D | | TB0272H | 10 | 2 | | 157, 167-199, 277-299 |
| 113 | 22 | PA | | 4-0 | 28-21-12 | D01090 | | X1 | | | TB0272H | 10 | 2 | | 050-099 |
| 113 | 22 | PA | | 5-0 | 28-21-12 | D01090 | | X1 | | | TB0272H | 10 | 2 | | 150-199, 275-299 |
| 114 | 22 | PA | | 6-0 | 28-21-12 | D04992J | | 2 | | | TB0272H | 10 | 2 | | 050-099 |
| 114 | 22 | PA | | 4-0 | 28-21-12 | D04992J | | 2 | | | TB0272H | 10 | 2 | | 150-199, 275-299 |
| 115 | 22 | PA | | 5-0 | 28-21-12 | D03548 | | X1 | | | TB0272H | 10 | 2 | | 050-099 |
| 115 | 22 | PA | | 6-0 | 28-21-12 | D03548 | | X1 | | | TB0272H | 10 | 2 | | 150-199, 275-299 |
| 116 | 22 | PA | | 6-0 | 28-21-11 | D03540 | | X2 | | | D04942J | 19 | | | ALL |
| 117 | 22 | PA | | 3-0 | 28-21-11 | D03540 | | X1 | | | TB0078Y | A002 | BJ | | ALL |
| 118 | 22 | PA | | 3-0 | 28-21-11 | D03542 | | X1 | | | TB0078Y | A002 | BJ | | ALL |
| 119 | 20 | PA | | 6-0 | 28-21-11 | D04942J | | 12 | | | TB0078Y | A002 | BJ | | ALL |
| 11A | 24 | PK | | 6-0 | 21-58-12 | D11538 | | 1 | | | TB0272Y | A032 | BJ | | 050-099 |
| 11A | 24 | PK | | 4-0 | 21-58-12 | D11538 | | 1 | | | TB0272Y | A032 | BJ | | 150-199, 275-299 |
| 11B | 24 | PK | | 6-0 | 21-58-12 | D11538 | | 6 | | | TB0272F | A015 | 2 | | 050-099 |
| 11B | 24 | PK | | 4-0 | 21-58-12 | D11538 | | 6 | | | TB0272F | A015 | 2 | | 150-199, 275-299 |
| 11C | 24 | PK | | 2-0 | 21-58-12 | D11538 | | 8 | | | D11550 | 6 | | | ALL |
| 11D | 24 | PK | | 6-0 | 21-58-12 | D11550 | | 1 | | | TB0272Y | A032 | BJ | | 050-099 |
| 11D | 24 | PK | | 4-0 | 21-58-12 | D11550 | | 1 | | | TB0272Y | A032 | BJ | | 150-199, 275-299 |
| 11E | 24 | PK | | 4-0 | 21-58-12 | D11550 | | 8 | | | TB0250Y | A010 | BJ | | 050-099 |
| 11E | 24 | PK | | 3-0 | 21-58-12 | D11550 | | 8 | | | TB0250Y | A010 | BJ | | 150-199, 275-299 |
| 11F | 24 | PK | | 6-0 | 21-58-12 | TB0272Y | | A032 | BJ | | TB0250Y | C010 | BJ | | 050-099 |
| 11F | 24 | PK | | 4-0 | 21-58-12 | TB0272Y | | A032 | BJ | | TB0250Y | C010 | BJ | | 150-199, 275-299 |
| 11G | 24 | PK | | 6-0 | 21-58-12 | D03596 | | C1 | | | TB0272Y | C032 | BJ | | 050-099 |
| 11G | 24 | PK | | 8-0 | 21-58-12 | D03596 | | C1 | | | TB0272Y | C032 | BJ | | 150-199, 275-299 |
| 11H | 20 | PA | | 6-0 | 21-58-12 | D03596 | | D3 | | | GDX0017 | D.. | 2 | * | 050-099 |
| 11H | 20 | UA | | 8-0 | 21-58-12 | D03596 | | D3 | | | GDX0017 | D.. | 2 | * | 150-199, 275-299 |
| 11J | 22 | PA | | 5-0 | 32-45-11 | D04743J | | 19 | | | TB0302Y | C024 | BJ | | 050-099 |
| 11J | 22 | PA | | 4-0 | 32-45-11 | TB0302Y | | C024 | BJ | | D04743J | 19 | | | 150-199 |
| 120 | 22 | PA | | 6-0 | 28-21-11 | D03542 | | X2 | | | D04942J | 18 | | | ALL |
| 121 | 22 | PA | | 6-0 | 28-21-11 | D03500 | | X2 | | | D04942J | 17 | | | ALL |
| 122 | 22 | PA | | 3-0 | 28-21-11 | D03500 | | X1 | | | TB0078Y | C002 | BJ | | ALL |
| 123 | 22 | PA | | 3-0 | 28-21-11 | D03502 | | X1 | | | TB0078Y | C002 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 15

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 124 | 20 | | PA | 6-0 | 28-21-11 | D04942J | | 11 | | | | | TB0078Y | C002 | BJ | | ALL |
| 125 | 22 | | PA | 6-0 | 28-21-11 | D03502 | | X2 | | | | | D04942J | 16 | | | ALL |
| 126 | 22 | | PA | 6-0 | 28-21-11 | D03544 | | X2 | | | | | D04942J | 14 | | | ALL |
| 127 | 22 | | PA | 3-0 | 28-21-11 | D03544 | | X1 | | | | | TB0078Y | A003 | BJ | | ALL |
| 129 | 22 | | PA | 6-0 | 28-21-11 | D04942J | | 13 | | | | | D03562 | X2 | | | ALL |
| 130 | 20 | | PA | 6-0 | 28-21-11 | TB0078Y | | A003 | BJ | | | | D04942J | 10 | | | ALL |
| 131 | 22 | | PA | 6-0 | 28-21-12 | D04992J | | 5 | | | | | TB0078Y | A004 | BJ | | ALL |
| 132 | 22 | | PA | 3-0 | 28-21-12 | D03548 | | A3 | | | | | TB0078Y | A004 | BJ | | ALL |
| 133 | 22 | | PA | 3-0 | 28-21-12 | D01090 | | X2 | | | | | TB0078Y | A004 | BJ | | ALL |
| 134 | 22 | | PA | 3-0 | 28-21-12 | D01090 | | A2 | | | | | TB0078Y | A004 | BJ | | ALL |
| 135 | 22 | | PA | 6-0 | 28-21-12 | D04992J | | 3 | | | | | D01090 | A1 | | | ALL |
| 136 | 20 | | PA | 3-0 | 28-21-12 | D03548 | | X2 | | | | | GDX0001 | D.. | 2 | | ALL |
| 137 | 20 | | PA | 3-0 | 28-21-12 | D03548 | | A2 | | | | | GDX0001 | D.. | 2 | | ALL |
| 138 | 20 | | PA | 6-0 | 28-21-13 | D03542 | | A1 | | | | | D04942J | 31 | | | ALL |
| 139 | 20 | | PA | 6-0 | 28-21-13 | D03500 | | A1 | | | | | D04942J | 32 | | | ALL |
| 140 | 20 | | PA | 6-0 | 28-21-13 | D03540 | | A1 | | | | | D04942J | 30 | | | ALL |
| 141 | 20 | | PA | 6-0 | 28-21-13 | D03502 | | A1 | | | | | D04942J | 29 | | | ALL |
| 142 | 20 | | PA | 6-0 | 28-21-13 | D03544 | | A1 | | | | | D04942J | 28 | | | ALL |
| 143 | 20 | | PA | 6-0 | 28-21-13 | D03562 | | A1 | | | | | D04942J | 27 | | | ALL |
| 144 | 20 | | PA | 2-0 | 28-21-13 | D03548 | | B1 | | | | | D01090 | B2 | | | ALL |
| 145 | 20 | | PA | 3-0 | 28-21-13 | TB0078Z | | 5 | BJ | | | | D01090 | B1 | | | ALL |
| 146 | 20 | | PA | 3-0 | 28-21-13 | D03540 | | A2 | | | | | TB0078Z | 5 | BJ | | ALL |
| 148 | 20 | | PA | 3-0 | 28-21-13 | TB0078Z | | 5 | BJ | | | | D03542 | A2 | | | ALL |
| 149 | 22 | | PA | 4-0 | 27-09-13 | TB0272D | | C035 | 2 | | | | D11444 | 4 | | | ALL |
| 150 | 20 | | PA | 3-0 | 28-21-13 | D03500 | | A2 | | | | | TB0078Z | 5 | BJ | | ALL |
| 152 | 20 | | PA | 3-0 | 28-21-13 | TB0078Z | | 5 | BJ | | | | D03502 | A2 | | | ALL |
| 153 | 22 | | PA | 6-0 | 28-21-13 | D04856J | | 33 | | | | | D03594 | D3 | | | ALL |
| 154 | 20 | | PA | 3-0 | 28-21-13 | D03544 | | A2 | | | | | TB0078Z | 5 | BJ | | ALL |
| 155 | 20 | | PA | 3-0 | 28-21-13 | D03562 | | A2 | | | | | TB0078Z | 5 | BJ | | ALL |
| 156 | 20 | | PA | 2-0 | 28-21-13 | D03548 | | B2 | | | | | D03594 | D2 | | | ALL |
| 157 | 20 | | PA | 6-0 | 28-21-13 | D03594 | | D1 | | | | | D04856J | 1 | | | ALL |
| 160 | 20 | | PA | 6-0 | 27-09-13 | D04856J | | 29 | | | | | D11444 | 3 | | | 050-099 |
| 160 | 20 | | PA | 5-0 | 27-09-13 | D04856J | | 29 | | | | | D11444 | 3 | | | 150-199, 275-299 |
| 161 | 22 | | PA | 6-0 | 27-09-13 | D05313J | | 5 | | | | | D11444 | 7 | | | 050-099 |
| 161 | 22 | | PA | 5-0 | 27-09-13 | D05313J | | 5 | | | | | D11444 | 7 | | | 150-199, 275-299 |
| 164 | 24 | | PK | 3-0 | 29-21-31 | D04942J | | 36 | | | | | D04856J | 12 | | | ALL |
| 165 | 22 | | PA | 4-0 | 27-09-13 | TB0272D | | C036 | 2 | | | | D11444 | 8 | | | ALL |
| 166 | 24 | | PK | 4-0 | 80-11-11 | D03526 | | X1 | | | | | TB0078Y | A014 | BJ | | ALL |
| 167 | 24 | | PK | 6-0 | 80-11-11 | D08026J | | 15 | | | | | TB0078Y | A014 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 16

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0184 | 286T0184 | | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | |
| 168 | 24 | | PK | | 6-0 | 80-11-11 | D08026J | | 16 | | | | D03530 | D2 | | ALL |
| 169 | 20 | | PA | | 3-0 | 80-11-11 | D03526 | | X2 | | | | GDX0001 | D.. | 2 | ALL |
| 16A | 22 | | PQ | AG | 15-0 | 28-42-12 | D08026J | | 41 | | | | TB0218Y | A005 | BJ | 150-154, 275 |
| 16AZ | | | | AG | 0-0 | 28-42-12 | D08026J | | DED | | | | TB0218Y | DED | | 150-154, 275 |
| 170 | 24 | | PK | | 4-0 | 80-11-11 | TB0078Y | | A014 | BJ | | | D03530 | D3 | | ALL |
| 171 | 20 | | PA | | 4-0 | 76-11-11 | D08026J | | 2 | | | | TB0216Z | 14 | BJ | 050-099, 150-154, 275-276 |
| 171 | 20 | | PA | | 7-0 | 76-11-11 | D08026J | | 2 | | | | TB0080Z | 4 | BJ | 155-199, 277-299 |
| 172 | 20 | | PA | | 4-0 | 76-11-11 | D08026J | | 49 | | | | TB0216Z | 14 | BJ | 050-099, 150-154, 275-276 |
| 172 | 20 | | PA | | 6-0 | 76-11-11 | D08026J | | 49 | | | | TB0080Z | 4 | BJ | 155-199, 277-299 |
| 173 | 20 | | PA | | 4-0 | 76-11-11 | D08026J | | 52 | | | | TB0272D | C034 | 2 | ALL |
| 174 | 20 | | PA | | 4-0 | 76-11-11 | D08026J | | 1 | | | | TB0216Y | A006 | BJ | ALL |
| 175 | 24 | | PK | | 5-0 | 76-11-11 | TB0216Z | | 14 | BJ | | | D03530 | X1 | | 050-099 |
| 175 | 24 | | PK | | 4-0 | 76-11-11 | TB0216Z | | 14 | BJ | | | D03530 | X1 | | 150-154, 275-276 |
| 175 | 24 | | PK | | 4-0 | 76-11-11 | TB0080Z | | 4 | BJ | | | D03530 | X1 | | 155-199, 277-299 |
| 176 | 20 | | PA | | 5-0 | 76-11-11 | TB0216Y | | A006 | BJ | | | D03530 | A2 | | ALL |
| 177 | 20 | | PA | | 3-0 | 76-11-11 | GDX0001 | | D.. | 2 | | | D03530 | X2 | | ALL |
| 178 | 20 | | PA | | 3-0 | 76-11-11 | TB0078Y | | C001 | BJ | | | D03530 | A1 | | 050-099 |
| 178 | 20 | | PA | | 4-0 | 76-11-11 | TB0078Y | | C001 | BJ | | | D03530 | A1 | | 150-199, 275-299 |
| 180 | 22 | | PA | | 6-0 | 76-11-11 | D03530 | | A3 | | | | D08026J | 10 | | 050-099, 275-299 |
| 180 | 20 | | PA | | 6-0 | 76-11-11 | D03530 | | A3 | | | | D08026J | 10 | | 150-154 |
| 180 | 22 | | PA | | 6-0 | 76-11-11 | D03530 | | A3 | BJ | | | D08026J | 10 | | 155-199 |
| 181 | 20 | | PA | | 3-0 | 27-09-13 | D11444 | | 5 | | | | GDX0012 | S.. | 2 | ALL |
| 182 | 20 | | PA | | 2-0 | 76-11-11 | TB0272D | | A034 | 2 | | | TB0216Z | 14 | BJ | 050-099 |
| 182 | 20 | | PA | | 3-0 | 76-11-11 | TB0272D | | A034 | 2 | | | TB0216Z | 14 | BJ | 150-154, 275-276 |
| 182 | 20 | | PA | | 6-0 | 76-11-11 | TB0272D | | A034 | 2 | | | TB0080Z | 4 | BJ | 155-199, 277-299 |
| 183 | 18 | | PA | | 6-0 | 32-71-11 | D11078 | | B1 | | | | TB0272F | A028 | 2 | 150-199, 275-299 |
| 184 | 18 | | PA | | 6-0 | 32-71-11 | D11078 | | B2 | | | | TB0272G | 30 | 2 | 150-199, 275-299 |
| 185 | 18 | | PA | | 6-0 | 32-71-11 | D11078 | | B3 | | | | TB0272F | C028 | 2 | 150-199, 275-299 |
| 186 | 24 | | PK | | 6-0 | 32-71-11 | D11078 | | X1 | | | | TB0272G | 30 | 2 | 150-199, 275-299 |
| 187 | 24 | | PK | | 6-0 | 32-71-11 | D11078 | | X2 | | | | TB0272F | A029 | 2 | 150-199, 275-299 |
| 195 | 24 | | PK | | 5-0 | 33-16-14 | D04743J | | 4 | | | | TB0220X | C016 | BJ | ALL |
| 198 | 18 | | PA | | 3-0 | 28-22-21 | D04942J | | 23 | DK | | | D08026J | 4 | DL | ALL |
| 199 | 18 | | PA | | 3-0 | 28-22-21 | D04942J | | 3 | DK | | | D08026J | 3 | DL | ALL |
| 203B | 22 | | PB | C | 4-0 | 27-51-41 | D08026J | | 23 | | | | TB0302X | B005 | BJ | 050-099 |
| 203B | 22 | | PB | C | 5-0 | 27-51-41 | D08026J | | 23 | | | | TB0302X | B005 | BJ | 150-199, 275-299 |
| 203R | 22 | | PB | C | 0-0 | 27-51-41 | D08026J | | 24 | | | | TB0302X | A005 | BJ | ALL |
| 204B | 24 | | PL | J | 3-0 | 28-41-11 | D04942J | | 20 | | | | TB0272X | B003 | BJ | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 17

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | | |
| 204B | 24 | PL | J | 4-0 | 28-41-11 | D04942J | | 20 | | | | TB0272X | B003 | BJ | | 150-199, 275-299 |
| 204R | 24 | PL | J | 0-0 | 28-41-11 | D04942J | | 21 | | | | TB0272Y | A005 | BJ | | ALL |
| 205B | 24 | PL | K | 5-0 | 28-41-11 | D03538 | | B2 | | | | TB0218F | C020 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 205B | 24 | PL | K | 6-0 | 28-41-11 | D03538 | | B2 | | | | TB0218F | C020 | 2 | | 157, 167-199, 277-299 |
| 205R | 24 | PL | K | 0-0 | 28-41-11 | D03538 | | B1 | | | | TB0218Y | A018 | BJ | | ALL |
| 206B | 24 | PL | M | 4-0 | 28-41-11 | TB0220X | | A003 | BJ | | | D04992J | 24 | | | ALL |
| 206R | 24 | PL | M | 0-0 | 28-41-11 | TB0220X | | B003 | BJ | | | D04992J | 25 | | | ALL |
| 207B | 24 | PL | L | 4-0 | 28-41-11 | TB0218F | | C020 | 2 | | | D04992J | 11 | | | ALL |
| 207R | 24 | PL | L | 0-0 | 28-41-11 | D04992J | | 19 | | | | TB0218Y | A018 | BJ | | ALL |
| 208B | 24 | PW | N | 4-0 | 73-21-14 | D05366J | | 14 | | | | TB0302Y | A016 | BJ | | ALL |
| 208R | 24 | PW | N | 0-0 | 73-21-14 | D05366J | | 15 | | | | TB0302Y | C016 | BJ | | ALL |
| 208Z | | | N | 0-0 | 73-21-14 | D05366J | | 16 | | | | TB0302Y | A018 | BJ | | ALL |
| 216 | 24 | PK | | 4-0 | 73-21-11 | D08026J | | 44 | | | | TB0218Y | A017 | BJ | | 050-099 |
| 216 | 24 | PK | | 4-0 | 73-21-11 | TB0218Y | | A017 | BJ | | | D08026J | 44 | | | 150-199, 277-299 |
| 216 | 24 | PK | | 4-0 | 73-21-11 | TB0218X | | C004 | BJ | | | D08026J | 44 | | | 275-276 |
| 217 | 24 | PK | | 4-0 | 73-21-11 | D08026J | | 43 | | | | TB0218Y | C017 | BJ | | 050-099 |
| 217 | 24 | PK | | 4-0 | 73-21-11 | TB0218Y | | C017 | BJ | | | D08026J | 43 | | | 150-199, 277-299 |
| 217 | 24 | PK | | 4-0 | 73-21-11 | TB0218X | | D004 | BJ | | | D08026J | 43 | | | 275-276 |
| 218B | 24 | PW | AB | 4-0 | 77-12-11 | D05366J | | 20 | | | | TB0318Y | CAP | Y | | 050-099 |
| 218B | 24 | PW | AB | 4-0 | 77-12-11 | TB0272Y | | CAP | Y | | | D05366J | 20 | | | 150-155, 275-276 |
| 218B | 24 | PW | AB | 4-0 | 77-12-11 | TB0272Y | | CAP | Y | | | D05366J | 20 | | | 156-157 |
| 218B | 24 | PW | AB | 4-0 | 77-12-11 | TB0318Y | | CAP | Y | | | D05366J | 20 | | | 162-165 |
| 218B | 24 | PW | AB | 4-0 | 77-12-11 | TB0318Y | | CAP | Y | | | D05366J | 20 | | | 166-199, 277-299 |
| 218R | 24 | PW | AB | 0-0 | 77-12-11 | D05366J | | 19 | | | | TB0318Y | CAP | Y | | 050-099 |
| 218R | 24 | PW | AB | 0-0 | 77-12-11 | TB0272Y | | CAP | Y | | | D05366J | 19 | | | 150-155, 275-276 |
| 218R | 24 | PW | AB | 0-0 | 77-12-11 | TB0272Y | | CAP | Y | | | D05366J | 19 | | | 156-157 |
| 218R | 24 | PW | AB | 0-0 | 77-12-11 | TB0318Y | | CAP | Y | | | D05366J | 19 | | | 162-165 |
| 218R | 24 | PW | AB | 0-0 | 77-12-11 | TB0318Y | | CAP | Y | | | D05366J | 19 | | | 166-199, 277-299 |
| 218Z | | | AB | 0-0 | 77-12-11 | D05366J | | 18 | | | | TB0318Y | DED | | | 050-099 |
| 218Z | | | AB | 0-0 | 77-12-11 | TB0272Y | | DED | | | | D05366J | 18 | | | 150-157, 275-276 |
| 218Z | | | AB | 0-0 | 77-12-11 | TB0318Y | | DED | | | | D05366J | 18 | | | 162-199, 277-299 |
| 401B | 24 | PN | D | 4-0 | 27-51-41 | D08026J | | 25 | | | | TB0302X | A004 | BJ | | 050-099 |
| 401B | 24 | PN | D | 5-0 | 27-51-41 | D08026J | | 25 | | | | TB0302X | A004 | BJ | | 150-199, 275-299 |
| 401G | 24 | PN | D | 0-0 | 27-51-41 | D08026J | | 28 | | | | TB0302X | D004 | BJ | | ALL |
| 401R | 24 | PN | D | 0-0 | 27-51-41 | D08026J | | 26 | | | | TB0302X | B004 | BJ | | ALL |
| 401Y | 24 | PN | D | 0-0 | 27-51-41 | D08026J | | 27 | | | | TB0302X | C004 | BJ | | ALL |
| 434 | 22 | PA | | 4-0 | 21-58-16 | D10462 | | C3 | | | | TB0078Y | C014 | BJ | | ALL |
| 501 | 20 | PA | | 3-0 | 28-22-31 | D04942J | | 5 | | | | D04856J | 5 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 18

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|------|----------|---------|-------|------|------|--------|-------|------|------|--------|-------------|------|----|--|--|---------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | | | | | | | |
| 501 | 20 | PA | | | 2-0 | 28-22-31 | D04942J | | 5 | | | | | | | D04856J | 5 | | | | 150-199, 275-299 |
| 503 | 22 | PA | | | 4-0 | 32-41-11 | D04992J | | 1 | | | | | | | TB0302Y | A015 | BJ | | | ALL |
| 504 | 20 | PA | | | 6-0 | 28-26-11 | D03594 | | B3 | | | | | | | D04856J | 30 | | | | ALL |
| 505 | 18 | PA | | | 6-0 | 28-26-11 | D03594 | | B1 | | | | | | | D04856J | 31 | | | | ALL |
| 506 | 20 | PA | | | 6-0 | 28-26-11 | D03538 | | D1 | | | | | | | D04992J | 17 | | | | ALL |
| 507 | 22 | PA | | | 4-0 | 32-41-11 | D04992J | | 18 | | | | | | | TB0302Y | A015 | BJ | | | ALL |
| 508 | 22 | PA | | | 4-0 | 32-41-11 | D04856J | | 3 | | | | | | | TB0302Y | A015 | BJ | | | ALL |
| 50R | 22 | PA | | | 4-0 | 32-45-11 | D04743J | | 20 | | | | | | | TB0272X | C014 | BJ | | | 050-099, 150-199 |
| 512 | 20 | PA | | | 2-0 | 27-11-12 | D05165J | | 1 | | | | | | | D04856J | 39 | | | | ALL |
| 513 | 20 | PA | | | 2-0 | 27-11-12 | D05165J | | 2 | | | | | | | D04856J | 38 | | | | ALL |
| 514 | 18 | PA | | | 2-0 | 27-11-12 | D05165J | | 3 | DL | | | | | | D04856J | 37 | | | | ALL |
| 515 | 18 | PA | | | 2-0 | 27-11-12 | D05165J | | 4 | DL | | | | | | D04856J | 32 | | | | ALL |
| 517 | 22 | PA | | | 6-0 | 29-11-32 | M00497 | | A | C | | | | | | TB0272D | A040 | 2 | | | ALL |
| 518 | 22 | PA | | | 4-0 | 29-11-32 | TB0080G | | 10 | 2 | | | | | | TB0078Y | C013 | BJ | | | 050-099 |
| 518 | 22 | PA | | | 2-0 | 29-11-32 | TB0080G | | 10 | 2 | | | | | | TB0078Y | C013 | BJ | | | 150-199, 275-299 |
| 519 | 22 | PA | | | 4-0 | 29-11-32 | TB0080D | | A002 | 2 | | | | | | TB0078Y | A011 | BJ | | | ALL |
| 51A | 20 | PA | | | 6-0 | 76-11-11 | D08026J | | 11 | | | | | | | TB0078Y | C001 | BJ | | | 050-099 |
| 51A | 20 | PA | | | 6-0 | 76-11-11 | TB0078Y | | C001 | BJ | | | | | | D08026J | 11 | | | | 150-199, 275-299 |
| 534 | 22 | PA | | | 3-0 | 28-21-11 | D03562 | | X1 | | | | | | | TB0078Y | A003 | BJ | | | ALL |
| 535 | 18 | PA | | | 6-0 | 28-21-11 | D04856J | | 27 | | | | | | | TB0078G | 16 | 2 | | | ALL |
| 536 | 24 | PK | | | 3-0 | 28-42-21 | D05366J | | 6 | | | | | | | D04942J | 2 | | | | ALL |
| 537 | 18 | PA | | | 5-0 | 28-26-11 | D03594 | | B2 | | | | | | | TB0222G | 5 | 2 | | | ALL |
| 538 | 20 | PA | | | 5-0 | 28-26-11 | D03538 | | D2 | | | | | | | TB0222G | 5 | 2 | | | ALL |
| 539 | 20 | PA | | | 3-0 | 28-26-11 | D02922 | | 7 | | | | | | | GDX0001 | D.. | 2 | | | ALL |
| 540 | 24 | PK | | | 5-0 | 28-26-11 | D02922 | | 3 | | | | | | | D04942J | 34 | | | | ALL |
| 542 | 20 | PA | | | 6-0 | 28-26-11 | D02928 | | A3 | | | | | | | D04942J | 38 | | | | ALL |
| 543 | 20 | PA | | | 2-0 | 28-26-11 | D02922 | | 5 | | | | | | | D02928 | B1 | | | | ALL |
| 544 | 20 | PA | | | 2-0 | 28-26-11 | D02922 | | 4 | | | | | | | D02928 | B3 | | | | ALL |
| 545 | 20 | PA | | | 3-0 | 28-26-11 | D02922 | | 2 | | | | | | | GDX0001 | D.. | 2 | | | ALL |
| 549 | 20 | PA | | | 6-0 | 28-26-11 | D02928 | | A1 | | | | | | | D04942J | 37 | | | | ALL |
| 550 | 20 | PA | | | 3-0 | 28-26-11 | D02928 | | X2 | | | | | | | GDX0002 | D.. | 2 | | | ALL |
| 551 | 20 | PA | | | 6-0 | 28-26-11 | D02928 | | X1 | | | | | | | D04992J | 26 | | | | 050-099 |
| 551 | 20 | PA | | | 5-0 | 28-26-11 | D02928 | | X1 | | | | | | | D04992J | 26 | | | | 150-199, 275-299 |
| 552 | 20 | PA | | | 5-0 | 28-26-11 | D02928 | | A2 | | | | | | | TB0222X | D007 | BJ | | | ALL |
| 553 | 20 | PA | | | 6-0 | 28-26-11 | D02928 | | B2 | | | | | | | D04992J | 27 | | | | 050-099 |
| 553 | 20 | PA | | | 5-0 | 28-26-11 | D02928 | | B2 | | | | | | | D04992J | 27 | | | | 150-199, 275-299 |
| 561 | 18 | PA | | | 11-0 | 28-21-11 | C00094 | | 2 | D | | | | | | D04942J | 15 | | | | 050-099, 150-156, 162-166, 275-276 |
| 561 | 18 | PA | | | 10-0 | 28-21-11 | C00094 | | 2 | D | | | | | | D04942J | 15 | DK | | | 157, 167-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0180
Page 19
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 562 | 24 | | PK | 5-0 | 28-26-11 | D02920 | | | 3 | | | | D08026J | 38 | | | ALL |
| 563 | 20 | | PA | 3-0 | 28-26-11 | D02920 | | | 7 | | | | GD00002 | D.. | 2 | | ALL |
| 564 | 20 | | PA | 6-0 | 28-26-11 | D08026J | | | 36 | | | | D02926 | A1 | | | ALL |
| 565 | 20 | | PA | 6-0 | 28-26-11 | D02926 | | | A3 | | | | D08026J | 37 | | | ALL |
| 566 | 20 | | PA | 2-0 | 28-26-11 | D02926 | | | B1 | | | | D02920 | 5 | | | ALL |
| 567 | 20 | | PA | 2-0 | 28-26-11 | D02926 | | | B3 | | | | D02920 | 4 | | | ALL |
| 568 | 20 | | PA | 3-0 | 28-26-11 | D02926 | | | X2 | | | | GD00002 | D.. | 2 | | ALL |
| 569 | 20 | | PA | 5-0 | 28-26-11 | D02926 | | | X1 | | | | D04992J | 30 | | | ALL |
| 570 | 20 | | PA | 5-0 | 28-26-11 | D02926 | | | A2 | | | | TB0222X | B008 | BJ | | ALL |
| 571 | 20 | | PA | 5-0 | 28-26-11 | D02926 | | | B2 | | | | D04992J | 31 | | | ALL |
| 579 | 24 | | PK | 4-0 | 21-58-16 | D10420 | | | 3 | | | | TB0220Y | C011 | BJ | | ALL |
| 581 | 24 | | PK | 6-0 | 21-58-16 | D05654J | | | 3 | | | | D03596 | A1 | | | 050-099 |
| 581 | 24 | | PK | 8-0 | 21-58-16 | D05654J | | | 3 | | | | D03596 | A1 | | | 150-199, 275-299 |
| 582 | 24 | | PK | 6-0 | 21-58-16 | D05654J | | | 2 | | | | D03596 | A3 | | | 050-099 |
| 582 | 24 | | PK | 8-0 | 21-58-16 | D05654J | | | 2 | | | | D03596 | A3 | | | 150-199, 275-299 |
| 583 | 24 | | PK | 5-0 | 21-58-16 | D03596 | | | B3 | | | | TB0220X | A014 | BJ | | ALL |
| 584 | 24 | | PK | 5-0 | 21-58-16 | D03596 | | | B1 | | | | TB0220X | B014 | BJ | | ALL |
| 585 | 24 | | PK | 5-0 | 21-58-12 | D03596 | | | X2 | | | | TB0218Y | C018 | BJ | | ALL |
| 586 | 24 | | PK | 3-0 | 21-58-12 | D03596 | | | X1 | | | | TB0078Z | 10 | BJ | | ALL |
| 587 | 24 | | PK | 3-0 | 21-58-16 | D03596 | | | A2 | | | | TB0080Y | A006 | BJ | | ALL |
| 588 | 24 | | PK | 6-0 | 21-58-12 | D03596 | | | B2 | | | | TB0218Y | A013 | BJ | | 050-099 |
| 588 | 24 | | PK | 8-0 | 21-58-12 | D03596 | | | B2 | | | | TB0218Y | A013 | BJ | | 150-199, 275-299 |
| 589 | 24 | | PK | 6-0 | 21-58-16 | D05654J | | | 5 | | | | TB0078Z | 10 | BJ | | 050-099 |
| 589 | 24 | | PK | 8-0 | 21-58-16 | D05654J | | | 5 | | | | TB0078Z | 10 | BJ | | 150-199, 275-299 |
| 590 | 24 | | PK | 3-0 | 21-58-16 | D10420 | | | 7 | | | | TB0078Z | 10 | BJ | | ALL |
| 593 | 24 | | PK | 2-0 | 21-58-16 | TB0078Z | | | 10 | BJ | | | TB0080Y | A006 | BJ | | ALL |
| 595 | 18 | | PA | 6-0 | 28-41-12 | D04942J | | | 22 | | | | D03538 | C1 | | | 050-099, 150-156, 162-166, 275-276 157, 167-199, 277-299 |
| 595 | 18 | | PA | 6-0 | 28-41-12 | D04942J | | | 22 | DK | | | D03538 | C1 | | | |
| 596 | 18 | | PA | 5-0 | 28-41-12 | D03538 | | | C2 | | | | TB0218G | 19 | 2 | | ALL |
| 598 | 18 | | PA | 5-0 | 28-41-12 | D03594 | | | A2 | | | | TB0218G | 19 | 2 | | ALL |
| 600 | 18 | | PA | 4-0 | 28-41-12 | D03594 | | | A1 | | | | TB0272G | 7 | 2 | | ALL |
| 603 | 18 | | PA | 4-0 | 28-41-12 | D04856J | | | 41 | | | | TB0272G | 7 | 2 | | ALL |
| 604 | 22 | | PA | 6-0 | 28-41-12 | D04856J | | | 40 | | | | D03594 | A3 | | | ALL |
| 607 | 22 | | PA | 4-0 | 23-71-11 | D03620 | | | 8 | | | | TB0218X | D002 | BJ | | ALL |
| 609 | 24 | | PK | 2-0 | 28-22-11 | D08026J | | | 31 | | | | D04856J | 10 | | | ALL |
| 610 | 24 | | PK | 4-0 | 28-25-11 | D08026J | | | 32 | | | | TB0272X | D002 | BJ | | ALL |
| 614 | 24 | | PK | 5-0 | 23-31-13 | D03526 | | | C3 | | | | TB0216X | C003 | BJ | | ALL |
| 615 | 24 | | PK | 5-0 | 23-31-13 | D03526 | | | C2 | | | | TB0216X | D003 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 20

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 638 | 24 | | PK | 3-0 | 29-11-32 | D10436 | | X2 | | | | | TB0078Y | A011 | BJ | | ALL |
| 640 | 20 | | PA | 3-0 | 29-11-32 | D10436 | | B1 | | | | | GDX0002 | D.. | 2 | | 050-099 |
| 640 | 20 | | PA | 2-0 | 29-11-32 | D10436 | | B1 | | | | | GDX0002 | D.. | 2 | | 150-199, 275-299 |
| 641 | 24 | | PK | 8-0 | 29-11-32 | D03524 | | X2 | | | | | M00497 | A | C | | ALL |
| 642 | 24 | | PK | 4-0 | 29-11-32 | D03524 | | B3 | | | | | TB0078Y | A011 | BJ | | ALL |
| 643 | 24 | | PK | 8-0 | 29-11-32 | D03524 | | B2 | | | | | M00305 | A | C | | ALL |
| 645 | 24 | | PK | 8-0 | 29-11-32 | D10436 | | B2 | | | | | M00305 | B | C | | ALL |
| 646 | 22 | | PA | 4-0 | 29-11-32 | D04856J | | 34 | | | | | TB0216Y | C009 | BJ | | ALL |
| 647 | 22 | | PA | 8-0 | 29-11-32 | TB0080D | | C001 | 2 | | | | M00922 | A | C | | ALL |
| 648 | 22 | | PA | 6-0 | 29-11-32 | TB0078Y | | C008 | BJ | | | | D04856J | 35 | | | ALL |
| 649 | 22 | | PA | 3-0 | 29-11-32 | D03626 | | B3 | | | | | TB0080D | A001 | 2 | | ALL |
| 64A | 22 | | PA | 4-0 | 30-34-11 | D08026J | | 40 | | | | | TB0302X | B006 | BJ | | 050-099 |
| 64A | 22 | | PA | 5-0 | 30-34-11 | D08026J | | 40 | | | | | TB0302X | B006 | BJ | | 150-199, 275-299 |
| 650 | 22 | | PA | 8-0 | 29-11-32 | D03626 | | B1 | | | | | M00919 | A | C | | ALL |
| 651 | 20 | | PA | 3-0 | 29-11-32 | D03626 | | X2 | | | | | GDX0002 | D.. | 2 | | ALL |
| 652 | 24 | | PK | 4-0 | 29-11-32 | D03626 | | X1 | | | | | TB0216Y | C001 | BJ | | ALL |
| 654 | 22 | | PA | 3-0 | 29-11-32 | D02252 | | B1 | | | | | TB0078Y | C008 | BJ | | ALL |
| 656 | 22 | | PA | 3-0 | 29-11-32 | D03626 | | B2 | | | | | TB0078Y | C008 | BJ | | ALL |
| 657 | 22 | | PA | 6-0 | 29-11-32 | D04856J | | 36 | | | | | TB0078Z | 6 | BJ | | ALL |
| 658 | 22 | | PA | 6-0 | 29-11-32 | D04856J | | 26 | | | | | M00919 | A | C | | 050-099 |
| 658 | 22 | | PA | 8-0 | 29-11-32 | D04856J | | 26 | | | | | M00919 | A | C | | 150-199, 275-299 |
| 659 | 18 | | PA | 6-0 | 29-11-32 | D04856J | | 23 | DL | | | | TB0080G | 10 | 2 | | ALL |
| 668 | 24 | | PK | 4-0 | 29-11-32 | D08026J | | 7 | | | | | TB0216Y | A002 | BJ | | ALL |
| 669 | 24 | | PK | 6-0 | 29-11-32 | D08026J | | 21 | | | | | TB0078Z | 6 | BJ | | ALL |
| 672 | 24 | | PK | 6-0 | 29-11-32 | D04992J | | 23 | | | | | TB0078Z | 6 | BJ | | ALL |
| 673 | 22 | | PA | 5-0 | 29-11-32 | D02252 | | A3 | | | | | TB0272D | C038 | 2 | | ALL |
| 674 | 24 | | PK | 3-0 | 29-11-32 | TB0216Y | | C001 | BJ | | | | D04992J | 21 | | | ALL |
| 676 | 22 | | PA | 6-0 | 29-11-32 | D04942J | | 4 | | | | | M00919 | B | C | | 050-099 |
| 676 | 22 | | PA | 7-0 | 29-11-32 | D04942J | | 4 | | | | | M00919 | B | C | | 150-199, 275-299 |
| 685 | 24 | | PK | 4-0 | 29-11-32 | D03524 | | X1 | | | | | TB0078Y | C013 | BJ | | ALL |
| 701 | 24 | | PK | 6-0 | 29-11-32 | TB0272D | | C040 | 2 | | | | TB0078Z | 6 | BJ | | ALL |
| 702 | 18 | | PA | 6-0 | 29-11-32 | D04992J | | 13 | DK | | | | D10436 | A1 | | | ALL |
| 703 | 24 | | PK | 5-0 | 29-11-32 | TB0272D | | A035 | 2 | | | | M00497 | B | C | | ALL |
| 704 | 24 | | PK | 5-0 | 29-11-32 | TB0272D | | A036 | 2 | | | | M00305 | B | C | | ALL |
| 707 | 22 | | PA | 2-0 | 28-22-31 | D04856J | | 19 | | | | | D04942J | 33 | | | 050-099 |
| 707 | 22 | | PA | 3-0 | 28-22-31 | D04856J | | 19 | | | | | D04942J | 33 | | | 150-199, 275-299 |
| 708 | 22 | | PA | 3-0 | 28-22-21 | D04942J | | 25 | | | | | D08026J | 35 | | | ALL |
| 70E | 18 | | PA | 4-0 | 38-32-11 | D04856J | | 43 | | | | | TB0302G | 19 | 2 | | 156-157, 166-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 21

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 70E | 18 | | PA | | 4-0 | 38-32-11 | D04856J | | 43 | | | | TB0302G | 32 | 2 | | 275-276 |
| 70R | 18 | | PA | | 4-0 | 38-32-11 | D04856J | | 42 | | | | TB0302F | C020 | 2 | | 156-157, 166-199, 277-299 |
| 70T | 18 | | PA | | 8-0 | 38-32-11 | D04856J | | 42 | | | | TB0076F | C015 | 2 | | 275-276 |
| 711 | 18 | | PA | | 5-0 | 21-24-11 | D02132 | | A1 | | | | TB0216F | C007 | 2 | | 050-099 |
| 711 | 18 | | PA | | 8-0 | 21-24-11 | D02132 | | A1 | | | | TB0216F | C007 | 2 | | 150-199 |
| 715 | 18 | | PA | | 5-0 | 21-24-11 | D02132 | | C2 | | | | TB0272F | A019 | 2 | | 050-099 |
| 715 | 18 | | PA | | 8-0 | 21-24-11 | D02132 | | C2 | | | | TB0272F | A019 | 2 | | 150-199 |
| 716 | 18 | | PA | | 5-0 | 21-24-11 | D02132 | | B2 | | | | TB0272F | C019 | 2 | | 050-099 |
| 716 | 18 | | PA | | 8-0 | 21-24-11 | D02132 | | B2 | | | | TB0272F | C019 | 2 | | 150-199 |
| 720 | 22 | | PQ | P | 5-0 | 74-31-11 | D03530 | | B2 | | | | TB0222X | B002 | BJ | | ALL |
| 720Z | | | | P | 0-0 | 74-31-11 | D03530 | | DED | | | | TB0222X | DED | | | ALL |
| 721 | 22 | | PA | | 5-0 | 74-31-11 | D03530 | | C2 | | | | TB0222X | B007 | BJ | | ALL |
| 722 | 22 | | PQ | Q | 5-0 | 74-31-11 | D03530 | | B3 | | | | TB0222X | C002 | BJ | | ALL |
| 722Z | | | | Q | 0-0 | 74-31-11 | D03530 | | DED | | | | TB0222X | DED | | | ALL |
| 723 | 22 | | PA | | 5-0 | 74-31-11 | D03530 | | C3 | | | | TB0222X | C007 | BJ | | ALL |
| 724 | 22 | | PA | | 4-0 | 32-41-11 | D04992J | | 9 | | | | TB0302X | A006 | BJ | | ALL |
| 726 | 22 | | PA | | 5-0 | 27-09-13 | D05313J | | 2 | | | | D11444 | 2 | | | ALL |
| 727 | 22 | | PA | | 5-0 | 27-09-13 | D05313J | | 4 | | | | D11444 | 6 | | | ALL |
| 728 | 22 | | PA | | 4-0 | 23-71-11 | D03620 | | 7 | | | | TB0218X | C002 | BJ | | ALL |
| 729 | 20 | | PA | | 3-0 | 28-26-11 | D02920 | | 2 | | | | GDX0002 | D.. | 2 | | ALL |
| 742 | 22 | | PA | | 7-0 | 29-11-32 | D04992J | | 15 | | | | S00572 | 1 | C | * | ALL |
| 743 | 22 | | PA | | 7-0 | 29-11-32 | TB0216Y | | C018 | BJ | | | S00572 | 2 | C | | ALL |
| 744 | 22 | | PA | | 7-0 | 29-11-32 | TB0216Y | | C018 | BJ | | | S00572 | 5 | C | | ALL |
| 745 | 22 | | PA | | 9-0 | 29-11-32 | D02252 | | Y1 | | | | S00572 | 6 | C | | ALL |
| 746 | 22 | | PA | | 9-0 | 29-11-32 | D02252 | | A2 | | | | S00572 | 2 | C | | ALL |
| 747 | 22 | | PA | | 9-0 | 29-11-32 | D02252 | | X1 | | | | S00572 | 1 | C | * | ALL |
| 748 | 20 | | PA | | 2-0 | 29-11-32 | D02252 | | B2 | | | | GDX0001 | D.. | 2 | | ALL |
| 749 | 20 | | PA | | 2-0 | 29-11-32 | D02252 | | X2 | | | | GDX0001 | D.. | 2 | | ALL |
| 750 | 20 | | PA | | 2-0 | 29-11-32 | D02252 | | Y2 | | | | GDX0001 | D.. | 2 | | ALL |
| 754 | 22 | | PA | | 6-0 | 21-58-16 | D06310J | | 15 | | | | TB0078Y | A013 | BJ | | ALL |
| 755 | 22 | | PA | | 4-0 | 21-58-16 | D10420 | | 4 | | | | TB0078Y | C014 | BJ | | ALL |
| 756 | 18 | | PA | | 7-0 | 21-24-11 | D02132 | | A2 | | | | TB0302F | C031 | 2 | | 050-099 |
| 756 | 18 | | PA | | 8-0 | 21-24-11 | D02132 | | A2 | | | | TB0302F | C030 | 2 | | 150-199 |
| 758 | 22 | | PA | | 6-0 | 28-21-11 | D04942J | | 7 | | | | TB0078Y | C003 | BJ | | ALL |
| 759 | 20 | | PA | | 4-0 | 28-22-31 | D04942J | | 6 | | | | D04856J | 6 | | | ALL |
| 75A | 24 | | PK | | 6-0 | 21-58-12 | D11546 | | 1 | | | | TB0272Y | C024 | BJ | | 050-099 |
| 75A | 24 | | PK | | 4-0 | 21-58-12 | D11546 | | 1 | | | | TB0272Y | C024 | BJ | | 150-199, 275-299 |
| 75B | 20 | | PA | | 2-0 | 21-58-12 | D11546 | | 6 | | | | GDX0017 | D.. | 2 | * | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 22

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|---|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | | | | |
| 75B | 20 | | UA | 2-0 | 21-58-12 | D11546 | | | | 6 | | | | GDX0017 | D.. | 2 | * | 150-199, 275-299 |
| 75C | 24 | | PK | 4-0 | 21-58-12 | D11546 | | | | 7 | | | | TB0272Y | A024 | BJ | | ALL |
| 75D | 24 | | PK | 8-0 | 21-58-12 | D11546 | | | | 3 | | | | D03596 | D2 | | | ALL |
| 75E | 24 | | PK | 4-0 | 21-58-12 | D11548 | | | | 5 | | | | TB0272Y | C024 | BJ | | ALL |
| 75F | 20 | | PA | 2-0 | 21-58-12 | D11548 | | | | 2 | | | | GDX0017 | D.. | 2 | | ALL |
| 75G | 24 | | PK | 3-0 | 21-58-12 | D11548 | | | | 7 | | | | TB0250X | A004 | BJ | | ALL |
| 75H | 24 | | PK | 3-0 | 21-58-12 | D11548 | | | | 3 | | | | TB0250D | A006 | 2 | | ALL |
| 75J | 24 | | PK | 6-0 | 21-58-12 | D11550 | | | | 5 | | | | TB0252Y | C002 | BJ | | ALL |
| 75K | 24 | | PK | 4-0 | 21-58-12 | D11550 | | | | 2 | | | | TB0250X | C003 | BJ | | 050-099 |
| 75K | 24 | | PK | 3-0 | 21-58-12 | D11550 | | | | 2 | | | | TB0250X | C003 | BJ | | 150-199, 275-299 |
| 75L | 24 | | PK | 6-0 | 21-58-12 | D11550 | | | | 4 | | | | TB0252Y | A002 | BJ | | ALL |
| 75M | 24 | | PK | 6-0 | 21-58-12 | D11550 | | | | 7 | | | | TB0252Z | 7 | BJ | | ALL |
| 75N | 24 | | PK | 6-0 | 21-58-12 | D11550 | | | | 3 | | | | TB0218Y | C018 | BJ | | 050-099 |
| 75N | 24 | | PK | 4-0 | 21-58-12 | D11550 | | | | 3 | | | | TB0218Y | C018 | BJ | | 150-199, 275-299 |
| 75P | 24 | | PK | 8-0 | 21-58-12 | D03596 | | | | | C3 | | | D06310J | 4 | | | ALL |
| 75R | 24 | | PK | 1-0 | 21-58-12 | TB0250D | | | | | C005 | 2 | | TB0250D | C006 | 2 | | ALL |
| 75S | 24 | | PK | 8-0 | 21-58-12 | TB0252Z | | | | | 7 | BJ | | TB0078Z | 10 | BJ | | ALL |
| 75T | 24 | | PK | 8-0 | 21-58-12 | D06310J | | | | | 10 | | | TB0250X | C004 | BJ | | ALL |
| 75U | 24 | | PK | 8-0 | 21-58-12 | D05654J | | | | | 8 | | | TB0252Y | A002 | BJ | | ALL |
| 75V | 24 | | PK | 8-0 | 21-58-12 | D05654J | | | | | 9 | | | TB0252Y | C002 | BJ | | ALL |
| 75W | 24 | | PK | 8-0 | 21-58-12 | D05654J | | | | | 4 | | | TB0250Y | A009 | BJ | | ALL |
| 75X | 24 | | PK | 8-0 | 21-58-12 | D05654J | | | | | 1 | | | TB0250Y | C009 | BJ | | ALL |
| 75Y | 24 | | PK | 4-0 | 21-58-12 | D04992J | | | | | 45 | | | TB0272Y | C024 | BJ | | ALL |
| 760 | 24 | | PK | 4-0 | 28-22-31 | D05366J | | | | | 4 | | | D04856J | 18 | | | ALL |
| 761 | 22 | | PA | 3-0 | 28-22-12 | D10068 | | | | | 3 | | | TB0078Y | C003 | BJ | | ALL |
| 762 | 22 | | PA | 3-0 | 28-22-12 | D10068 | | | | | 7 | | | TB0078G | 15 | 2 | | ALL |
| 763 | 24 | | PK | 10-0 | 28-22-12 | D10068 | | | | | 5 | | | D04856J | 22 | | | ALL |
| 764 | 20 | | PA | 3-0 | 28-22-12 | D10068 | | | | | 2 | | | GDX0002 | D.. | 2 | | ALL |
| 765 | 24 | | PV | A | 4-0 | 28-22-12 | D10068 | | | | 1 | | | TB0216Y | C010 | BJ | | ALL |
| 765Z | | | | A | 0-0 | 28-22-12 | D10068 | | | | | DED | | TB0216Y | DED | | | ALL |
| 766 | 20 | | PA | A | 3-0 | 28-22-12 | D10068 | | | | 6 | | | GDX0002 | D.. | 2 | | ALL |
| 768 | 24 | | PV | B | 15-0 | 28-22-12 | D04992J | | | | 42 | | | TB0218Y | C005 | BJ | | ALL |
| 768Z | | | | B | 0-0 | 28-22-12 | D04992J | | | | | DED | | TB0218Y | DED | | | ALL |
| 769 | 22 | | PA | | 7-0 | 34-12-11 | D04743J | | | | 9 | | | T00139 | LV | D | | ALL |
| 76A | 24 | | PK | | 4-0 | 21-58-12 | TB0250Y | | | | | A009 | BJ | TB0220X | A006 | BJ | | ALL |
| 76B | 24 | | PK | | 4-0 | 21-58-12 | TB0250Y | | | | | C009 | BJ | TB0220X | B006 | BJ | | ALL |
| 770 | 22 | | PA | | 7-0 | 34-12-11 | D04743J | | | | 10 | | | T00139 | GND | D | | ALL |
| 771 | 22 | | PA | | 7-0 | 34-12-11 | D04743J | | | | 11 | | | T00139 | HV | D | | ALL |
| 773 | 24 | | PK | | 6-0 | 21-58-11 | D11544 | | | | 2 | | | TB0222X | A013 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11
 Section W0180
 Page 23
 Aug 05/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | |
| 773 | 24 | | PK | | 4-0 | 21-58-11 | D11544 | | | | | | | | 150-199, 275-299 |
| 774 | 24 | | PK | | 5-0 | 21-58-12 | D03596 | | | | | | | | ALL |
| 776 | 22 | | PA | | 3-0 | 21-58-16 | D10420 | | | | | | | | ALL |
| 777 | 22 | | PA | | 4-0 | 29-11-32 | D04992J | | | | | | | | ALL |
| 779 | 24 | | PK | | 2-0 | 29-21-31 | D04942J | | | | | | | | 050-099 |
| 779 | 24 | | PK | | 3-0 | 29-21-31 | D04942J | | | | | | | | 150-199, 275-299 |
| 781 | 24 | | PK | | 4-0 | 32-41-11 | D05366J | | | | | | | | ALL |
| 782 | 24 | | PK | | 5-0 | 32-42-11 | D05366J | | | | | | | | ALL |
| 783 | 22 | | PA | | 5-0 | 32-42-11 | D10194 | | | | | | | | ALL |
| 784 | 22 | | PA | | 4-0 | 32-42-11 | TB0272D | A039 | | 2 | | | | | ALL |
| 785 | 22 | | PA | | 4-0 | 32-42-11 | D10196 | A3 | | | | | | | ALL |
| 786 | 22 | | PA | | 6-0 | 32-42-11 | TB0272D | C039 | | 2 | | | | | ALL |
| 787 | 24 | | PK | | 6-0 | 32-42-11 | D05366J | | | | | | | | ALL |
| 788 | 22 | | PA | | 4-0 | 32-42-11 | D10198 | A3 | | | | | | | ALL |
| 789 | 22 | | PA | | 4-0 | 32-42-11 | D10200 | A3 | | | | | | | ALL |
| 790 | 22 | | PA | | 4-0 | 32-42-11 | D10202 | A3 | | | | | | | ALL |
| 791 | 20 | | PA | | 3-0 | 32-42-11 | D10194 | A3 | | | | | | | ALL |
| 792 | 22 | | PA | | 5-0 | 32-42-11 | D10194 | B3 | | | | | | | 050-099 |
| 792 | 22 | | PA | | 4-0 | 32-42-11 | D10194 | B3 | | | | | | | 150-199, 275-299 |
| 793 | 24 | | PK | | 4-0 | 32-42-11 | D10194 | X1 | | | | | | | ALL |
| 794 | 24 | | PK | | 4-0 | 32-42-11 | D10194 | X2 | | | | | | | ALL |
| 795 | 20 | | PA | | 3-0 | 32-42-11 | D10196 | A2 | | | | | | | ALL |
| 796 | 24 | | PK | | 4-0 | 32-42-11 | D10196 | X2 | | | | | | | ALL |
| 797 | 24 | | PK | | 4-0 | 32-42-11 | D10196 | X1 | | | | | | | ALL |
| 798 | 20 | | PA | | 3-0 | 32-42-11 | D10198 | A2 | | | | | | | ALL |
| 799 | 24 | | PK | | 4-0 | 32-42-11 | D10198 | X2 | | | | | | | ALL |
| 801 | 24 | | PK | | 4-0 | 32-42-11 | D10198 | X1 | | | | | | | ALL |
| 802 | 20 | | PA | | 3-0 | 32-42-11 | D10200 | A2 | | | | | | | ALL |
| 803 | 24 | | PK | | 5-0 | 32-42-11 | D10200 | X2 | | | | | | | ALL |
| 804 | 24 | | PK | | 5-0 | 32-42-11 | D10200 | X1 | | | | | | | ALL |
| 805 | 20 | | PA | | 3-0 | 32-42-11 | D10202 | A2 | | | | | | | ALL |
| 806 | 24 | | PK | | 5-0 | 32-42-11 | D10202 | X2 | | | | | | | ALL |
| 807 | 24 | | PK | | 5-0 | 32-42-11 | D10202 | X1 | | | | | | | ALL |
| 808 | 24 | | PK | | 4-0 | 32-44-11 | D05366J | | | | | | | | ALL |
| 809 | 22 | | PA | | 4-0 | 32-44-11 | D08026J | | | | | | | | ALL |
| 814 | 22 | | PA | | 4-0 | 27-23-11 | D05366J | | | | | | | | ALL |
| 816R | 22 | | PH | | 4-0 | 26-17-11 | D04856J | | | | | | | | ALL |
| 818 | 24 | | PK | | 4-0 | 29-11-32 | D05366J | | | | | | | | ALL |
| 819 | 22 | | PA | | 5-0 | 29-11-32 | M00922 | | | | | | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 24

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|---------------------------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | |
| 819 | 22 | PA | | | 6-0 | 29-11-32 | M00922 | | B | C | | | | | 150-199, 275-299 |
| 821 | 24 | PK | | | 4-0 | 28-25-11 | D04856J | | 16 | | | | | | ALL |
| 823 | 22 | PA | | | 4-0 | 29-11-32 | D04992J | | 6 | | | | | | ALL |
| 824 | 20 | PA | | | 5-0 | 29-11-32 | TB0272D | A038 | 2 | | | | | | 050-099 |
| 824 | 20 | PA | | | 6-0 | 29-11-32 | TB0272D | A038 | 2 | | | | | | 150-199, 275-299 |
| 825 | 20 | PA | | | 3-0 | 32-42-11 | D10196 | | B2 | | | | | | ALL |
| 826 | 22 | PA | | | 2-0 | 32-42-11 | D10196 | | B3 | | | | | | ALL |
| 827 | 22 | PA | | | 2-0 | 32-42-11 | D10198 | | B3 | | | | | | ALL |
| 828 | 22 | PA | | | 2-0 | 32-42-11 | D10200 | | B3 | | | | | | ALL |
| 829 | 22 | PA | | | 5-0 | 32-42-11 | D10202 | | B3 | | | | | | 050-099 |
| 829 | 22 | PA | | | 5-0 | 32-42-11 | D10202 | | B3 | | | | | | 150-199 |
| 829 | 22 | PA | | | 5-0 | 32-42-11 | D10202 | | B3 | | | | | | 275-299 |
| 830 | 24 | PK | | | 4-0 | 32-42-11 | D05366J | | 13 | | | | | | ALL |
| 831 | 24 | PK | | | 5-0 | 21-58-16 | D10462 | | D3 | | | | | | ALL |
| 832 | 24 | PK | | | 5-0 | 21-58-16 | D10462 | | A3 | | | | | | ALL |
| 833 | 24 | PK | | | 5-0 | 21-58-16 | D10462 | | B3 | | | | | | ALL |
| 835 | 24 | PK | | | 4-0 | 29-11-32 | D04942J | | 1 | | | | | | ALL |
| 836 | 24 | PK | | | 4-0 | 29-11-32 | D04942J | | 9 | | | | | | ALL |
| 837 | 18 | PA | | | 4-0 | 28-41-12 | D04856J | | 28 | | | | | | ALL |
| 838 | 22 | PA | | | 4-0 | 28-41-12 | D04992J | | 40 | | | | | | ALL |
| 839 | 18 | PA | | | 3-0 | 29-11-32 | D10436 | | A2 | | | | | | ALL |
| 840 | 24 | PK | | | 3-0 | 29-11-32 | D10436 | | X1 | | | | | | ALL |
| 841 | 24 | PK | | | 3-0 | 29-11-32 | TB0080D | C002 | 2 | | | | | | 050-099 |
| 841 | 24 | PK | | | 2-0 | 29-11-32 | TB0080D | C002 | 2 | | | | | | 150-199, 275-299 |
| 842 | 24 | PK | | | 5-0 | 21-58-16 | D10462 | | A2 | | | | | | ALL |
| 843 | 24 | PK | | | 5-0 | 21-58-16 | D10462 | | B2 | | | | | | ALL |
| 845 | 24 | PK | | | 4-0 | 21-58-16 | D10420 | | 6 | | | | | | ALL |
| 846 | 24 | PK | | | 2-0 | 21-58-16 | D10422 | | B2 | | | | | | ALL |
| 847 | 20 | PA | | | 3-0 | 21-58-16 | D10422 | | B3 | | | | | | ALL |
| 849 | 24 | PK | | | 8-0 | 21-58-11 | D11544 | | 4 | | | | | | 050-099, 150-155, 162-165, 275-276 |
| 849 | 24 | PK | | | 8-0 | 21-58-11 | D11544 | | 4 | | | | | | 156-157, 166-199, 277-299 |
| 850 | 24 | PK | | | 5-0 | 21-58-16 | D10462 | | X2 | | | | | | 050-099 |
| 850 | 24 | PK | | | 4-0 | 21-58-16 | D10462 | | X2 | | | | | | 150-199, 275-299 |
| 851 | 24 | PK | | | 3-0 | 21-58-16 | D10462 | | X1 | | | | | | 050-099 |
| 851 | 24 | PK | | | 5-0 | 21-58-16 | D10462 | | X1 | | | | | | 150-199, 275-299 |
| 852 | 24 | PK | | | 5-0 | 21-58-16 | D10462 | | D2 | | | | | | ALL |
| 853 | 24 | PK | | | 2-0 | 21-58-16 | TB0272D | C021 | 2 | | | | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 25

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | | |
| 853 | 24 | | PK | 1-0 | 21-58-16 | TB0272D | C021 | 2 | | | | TB0272Z | 16 | BJ | | 150-199, 275-299 |
| 855 | 24 | | PK | 5-0 | 21-24-11 | D02132 | | X1 | | | | TB0218Y | A014 | BJ | | 050-099, 150-199 |
| 856 | 24 | | PK | 5-0 | 21-24-11 | D02132 | | X2 | | | | TB0218X | C012 | BJ | | 050-099, 150-199 |
| 857 | 22 | | PA | 5-0 | 31-31-11 | D03526 | | B3 | | | | TB0218X | A012 | BJ | | 050-099 |
| 857 | 22 | | PA | 6-0 | 31-31-11 | TB0218X | A012 | BJ | | | | D03526 | B3 | | | 150-199, 275-299 |
| 858 | 18 | | PA | 5-0 | 21-24-11 | D02132 | | B1 | | | | TB0216F | A008 | 2 | | 050-099 |
| 858 | 18 | | UA | 5-0 | 21-24-11 | D02132 | | B1 | | | | TB0216F | A008 | 2 | | 150-199 |
| 859 | 18 | | PA | 5-0 | 21-24-11 | D02132 | | C1 | | | | TB0216F | C008 | 2 | | 050-099, 150-199 |
| 860 | 24 | | PK | 8-0 | 31-31-13 | D05366J | | 7 | | | | TB0250X | A003 | BJ | | 050-099 |
| 860 | 24 | | PK | 7-0 | 31-31-13 | D05366J | | 7 | | | | TB0250X | A003 | BJ | | 150-199, 275-299 |
| 864 | 22 | | PA | 6-0 | 24-25-11 | D06470J | | 1 | | | | TB0302X | B007 | BJ | | 050-099 |
| 864 | 22 | | PA | 5-0 | 24-25-11 | D06470J | | 1 | | | | TB0302X | B007 | BJ | | 150-199, 275-299 |
| 865 | 22 | | PA | 6-0 | 24-25-11 | D06470J | | 2 | | | | TB0302X | D007 | BJ | | 050-099 |
| 865 | 22 | | PA | 5-0 | 24-25-11 | D06470J | | 2 | | | | TB0302X | D007 | BJ | | 150-199, 275-299 |
| 866 | 24 | | PK | 6-0 | 24-25-13 | D06470J | | 3 | | | | TB0302X | A008 | BJ | | 050-099 |
| 866 | 24 | | PK | 5-0 | 24-25-13 | D06470J | | 3 | | | | TB0302X | A008 | BJ | | 150-199, 275-299 |
| 867 | 24 | | PK | 6-0 | 24-25-13 | D06470J | | 4 | | | | TB0302X | B008 | BJ | | 050-099 |
| 867 | 24 | | PK | 5-0 | 24-25-13 | D06470J | | 4 | | | | TB0302X | B008 | BJ | | 150-199, 275-299 |
| 868 | 24 | | PK | 6-0 | 24-25-13 | D06470J | | 5 | | | | TB0302X | C008 | BJ | | 050-099 |
| 868 | 24 | | PK | 5-0 | 24-25-13 | D06470J | | 5 | | | | TB0302X | C008 | BJ | | 150-199, 275-299 |
| 869 | 24 | | PK | 6-0 | 24-25-13 | D06470J | | 6 | | | | TB0302X | D008 | BJ | | 050-099 |
| 869 | 24 | | PK | 5-0 | 24-25-13 | D06470J | | 6 | | | | TB0302X | D008 | BJ | | 150-199, 275-299 |
| 870 | 22 | | PA | 8-0 | 29-11-32 | D06470J | | 7 | | | | TB0078Z | 6 | BJ | | ALL |
| 878 | 24 | | PK | 8-0 | 21-58-12 | D03578 | | B1 | | | | D06310J | 2 | | | ALL |
| 879 | 24 | | PK | 8-0 | 21-58-12 | D03578 | | B2 | | | | TB0218Y | A013 | BJ | | 050-099 |
| 879 | 24 | | PK | 4-0 | 21-58-12 | D03578 | | B2 | | | | TB0218Y | A013 | BJ | | 150-199, 275-299 |
| 880 | 24 | | PK | 6-0 | 21-58-12 | D03578 | | B3 | | | | D06310J | 1 | | | ALL |
| 881 | 24 | | PK | 4-0 | 21-58-12 | TB0272Y | C032 | BJ | | | | D06310J | 3 | | | 050-099 |
| 881 | 24 | | PK | 8-0 | 21-58-12 | TB0272Y | C032 | BJ | | | | D06310J | 3 | | | 150-199, 275-299 |
| 882 | 24 | | PK | 4-0 | 21-58-12 | D11538 | | 5 | | | | TB0250Y | A008 | BJ | | 050-099 |
| 882 | 24 | | PK | 3-0 | 21-58-12 | D11538 | | 5 | | | | TB0250Y | A008 | BJ | | 150-199, 275-299 |
| 883 | 24 | | PK | 4-0 | 21-58-12 | D11538 | | 2 | | | | TB0250X | B004 | BJ | | 050-099 |
| 883 | 24 | | PK | 3-0 | 21-58-12 | D11538 | | 2 | | | | TB0250X | B004 | BJ | | 150-199, 275-299 |
| 884 | 24 | | PK | 4-0 | 21-58-12 | D11538 | | 4 | | | | TB0250Y | C008 | BJ | | 050-099 |
| 884 | 24 | | PK | 3-0 | 21-58-12 | D11538 | | 4 | | | | TB0250Y | C008 | BJ | | 150-199, 275-299 |
| 885 | 24 | | PK | 6-0 | 21-58-12 | D11538 | | 7 | | | | TB0252Z | 6 | BJ | | ALL |
| 886 | 24 | | PK | 6-0 | 21-58-12 | D11538 | | 3 | | | | TB0272Y | C023 | BJ | | 050-099 |
| 886 | 24 | | PK | 4-0 | 21-58-12 | D11538 | | 3 | | | | TB0272Y | C023 | BJ | | 150-199, 275-299 |
| 887 | 24 | | PK | 4-0 | 21-58-12 | D11540 | | 5 | | | | TB0250Y | A007 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 26

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0184 | 286T0184 | | | P36-S2-INTEGRATION (continued) | | | | | | | | | | | |
| 887 | 24 | | PK | | 3-0 | 21-58-12 | D11540 | | | | TB0250Y | A007 | BJ | | 150-199, 275-299 |
| 888 | 24 | | PK | | 4-0 | 21-58-12 | D11540 | | | | TB0250X | D003 | BJ | | 050-099 |
| 888 | 24 | | PK | | 3-0 | 21-58-12 | D11540 | | | | TB0250X | D003 | BJ | | 150-199, 275-299 |
| 889 | 24 | | PK | | 4-0 | 21-58-12 | D11540 | | | | TB0250Y | C007 | BJ | | 050-099 |
| 889 | 24 | | PK | | 3-0 | 21-58-12 | D11540 | | | | TB0250Y | C007 | BJ | | 150-199, 275-299 |
| 890 | 24 | | PK | | 6-0 | 21-58-12 | D11540 | | | | TB0252Z | 6 | BJ | | ALL |
| 891 | 24 | | PK | | 4-0 | 21-58-12 | D11540 | | | | TB0250D | A005 | 2 | | 050-099 |
| 891 | 24 | | PK | | 3-0 | 21-58-12 | D11540 | | | | TB0250D | A005 | 2 | | 150-199, 275-299 |
| 892 | 24 | | PK | | 6-0 | 21-58-12 | D11542 | | | | TB0272Y | A024 | BJ | | 050-099 |
| 892 | 24 | | PK | | 4-0 | 21-58-12 | D11542 | | | | TB0272Y | A024 | BJ | | 150-199, 275-299 |
| 893 | 24 | | PK | | 6-0 | 21-58-12 | D11542 | | | | TB0252Z | 6 | BJ | | ALL |
| 894 | 24 | | PK | | 6-0 | 21-58-12 | D11542 | | | | TB0252Z | 7 | BJ | | ALL |
| 895 | 24 | | PK | | 4-0 | 21-58-12 | D11542 | | | | TB0250X | D004 | BJ | | 050-099 |
| 895 | 24 | | PK | | 3-0 | 21-58-12 | D11542 | | | | TB0250X | D004 | BJ | | 150-199, 275-299 |
| 896 | 24 | | PK | | 6-0 | 21-58-12 | D11544 | | | | TB0252Z | 7 | BJ | | ALL |
| 897 | 24 | | PK | | 4-0 | 21-58-12 | D11544 | | | | TB0250Y | C008 | BJ | | 050-099 |
| 897 | 24 | | PK | | 3-0 | 21-58-12 | D11544 | | | | TB0250Y | C008 | BJ | | 150-199, 275-299 |
| 898 | 24 | | PK | | 4-0 | 21-58-12 | D11546 | | | | TB0250X | C004 | BJ | | 050-099 |
| 898 | 24 | | PK | | 3-0 | 21-58-12 | D11546 | | | | TB0250X | C004 | BJ | | 150-199, 275-299 |
| 899 | 20 | | PA | | 2-0 | 21-58-12 | D11546 | | | | GDY0017 | D.. | 2 | | ALL |
| 91C | 24 | | PV | DP | 4-0 | 73-21-14 | D06310J | | | | TB0302X | A001 | BJ | | 050-099 |
| 91C | 24 | | PV | AA | 8-0 | 73-21-14 | D06310J | | | | TB0302X | A001 | BJ | | 150-199, 275-299 |
| 91CZ | | | | DP | 0-0 | 73-21-14 | D06310J | | | | TB0302X | B002 | BJ | | 050-099 |
| 91CZ | | | | AA | 0-0 | 73-21-14 | D06310J | | | | TB0302X | B002 | BJ | | 150-199, 275-299 |
| 91M | 20 | | PA | | 4-0 | 76-11-11 | D08026J | | | | TB0272Y | C005 | BJ | | ALL |
| 91N | 20 | | PA | | 4-0 | 76-11-11 | D08026J | | | | TB0272Y | C005 | BJ | | 050-099 |
| 91N | 20 | | PA | | 8-0 | 76-11-11 | TB0272Y | C005 | BJ | | D08026J | 12 | | | 150-199, 275-299 |
| PA1 | | | | | 0-0 | 99-99-99 | D02132 | | | | D02132 | G2 | | | 050-099, 150-199 |
| W0185 | 286T0185 | | | E5-1 C,SHELF | | | | | | | | | | | |
| 002 | 20 | | PA | | 3-0 | 34-33-31 | D00405C | | | | GDY0001 | D.. | 2 | | 050-099 |
| 002 | 20 | | PA | | 1-8 | 34-33-31 | D00405C | | | | GDY0001 | D.. | 2 | | 150-199, 275-299 |
| 003 | 20 | | PA | | 3-0 | 34-33-31 | D00405C | | | | GDY0001 | A.. | 2 | | ALL |
| 004 | 24 | | PK | | 0-3 | 34-33-31 | D00405B | | | J04 | D00405B | J06 | | | ALL |
| 005 | 24 | | PK | | 0-3 | 34-33-31 | D00405B | | | C05 | D00405B | C06 | | | ALL |
| 006 | 24 | | PK | | 5-0 | 22-12-31 | D00405B | | | K06 | D04419P | 6 | | | 050-099 |
| 006 | 24 | | PK | | 6-0 | 22-12-31 | D00405B | | | K06 | D04419P | 6 | | | 150-199, 275-299 |
| 007 | 24 | | PK | | 3-0 | 34-33-31 | D00405B | | | G05 | TB0165F | C001 | 2 | | ALL |
| 009 | 24 | | PK | | 0-3 | 34-33-31 | D00405B | | | F02 | D00405B | F03 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0180
Page 27
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------|----|---------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0185 | 286T0185 | | | E5-1 C,SHELF (continued) | | | | | | | | | | | | |
| 010 | 24 | | PK | | 5-0 | 34-33-31 | D00405B | F04 | | | D04419P | 5 | | | 050-099 | |
| 010 | 24 | | PK | | 6-0 | 34-33-31 | D00405B | F04 | | | D04419P | 5 | | | 150-199, 275-299 | |
| 028 | 24 | | PK | | 3-0 | 34-33-31 | D00405B | F05 | | | GD0001 | D.. | 2 | | 050-099 | |
| 028 | 24 | | PK | | 1-8 | 34-33-31 | D00405B | F05 | | | GD0001 | D.. | 2 | | 150-199, 275-299 | |
| 029 | 24 | | PK | | 3-0 | 34-33-31 | D00405B | F06 | | | GD0001 | D.. | 2 | | 050-099 | |
| 029 | 24 | | PK | | 1-8 | 34-33-31 | D00405B | F06 | | | GD0001 | D.. | 2 | | 150-199, 275-299 | |
| 030 | 20 | | PQ | BE | 5-0 | 34-33-31 | D00405C | 8 | | | D05189P | 2 | | | 050-099 | |
| 030 | 20 | | PQ | BE | 6-0 | 34-33-31 | D00405C | 8 | | | D05189P | 2 | | | 150-199, 275-299 | |
| 030Z | | | | BE | 0-0 | 34-33-31 | D00405C | DED | | | D05189P | DED | | | ALL | |
| 201 | 20 | | UA | | 1-6 | 34-22-39 | D00405B | REF | | IA | GD0001 | S.. | 2 | | ALL | |
| 201B | 24 | | PW | IA | 4-0 | 34-22-39 | D00405B | G03 | | | D04419P | 3 | | | ALL | |
| 201R | 24 | | PW | IA | 0-0 | 34-22-39 | D00405B | G02 | | | D04419P | 2 | | | ALL | |
| 201Z | | | | IA | 0-0 | 34-22-39 | D00405B | REF | | IA | D04419P | 1 | | | ALL | |
| 202 | 20 | | UA | | 1-6 | 22-12-31 | D00405B | REF | | IB | GD0001 | S.. | 2 | | ALL | |
| 202B | 24 | | PW | IB | 4-0 | 22-12-31 | D00405B | B03 | | | D04419P | 8 | | | ALL | |
| 202R | 24 | | PW | IB | 0-0 | 22-12-31 | D00405B | B02 | | | D04419P | 7 | | | ALL | |
| 202Z | | | | IB | 0-0 | 22-12-31 | D00405B | REF | | IB | D04419P | 9 | | | ALL | |
| W0188 | 286T0188 | | | P37-L2-INTEGRATION | | | | | | | | | | | | |
| 001 | 22 | | PA | | 3-0 | 28-42-11 | D05506J | 1 | | | TB0304Y | C013 | BJ | | ALL | |
| 002 | 22 | | PA | | 4-7 | 78-36-21 | TB0274X | A013 | BJ | | D05372J | 12 | | | ALL | |
| 006 | 24 | | PK | | 4-6 | 21-58-16 | D05506J | 11 | | | TB0210X | C019 | BJ | | ALL | |
| 012 | 24 | | PK | | 4-6 | 21-61-21 | D05506J | 7 | | | TB0210Z | 12 | BJ | | 050-099 | |
| 012 | 24 | | PK | | 4-6 | 21-61-21 | TB0210Z | 12 | BJ | | D05506J | 7 | | | 150-199, 275-299 | |
| 013 | 24 | | PK | | 3-3 | 21-61-21 | D05506J | 10 | | | TB0320Y | A033 | BJ | | 050-099 | |
| 013 | 24 | | PK | | 3-3 | 21-61-21 | TB0320Y | A033 | BJ | | D05506J | 10 | | | 150-199, 275-299 | |
| 014 | 24 | | PK | | 3-3 | 21-61-21 | D05506J | 21 | | | TB0320Y | C033 | BJ | | 050-099 | |
| 014 | 24 | | PK | | 4-6 | 21-61-21 | TB0210Y | A001 | BJ | | D05506J | 21 | | | 150-199, 275-278 | |
| 014 | 24 | | PK | | 3-3 | 21-61-21 | TB0320Y | C033 | BJ | | D05506J | 21 | | | 280-299 | |
| 015 | 24 | | PK | | 4-0 | 24-22-11 | D05506J | 13 | | | TB0190Y | C010 | BJ | | ALL | |
| 016 | 22 | | PQ | E | 1-7 | 29-11-31 | D05506J | 16 | | | D04934J | 3 | | | ALL | |
| 016Z | | | | E | 0-0 | 29-11-31 | D05506J | DED | | | D04934J | DED | | | ALL | |
| 017 | 24 | | PK | | 4-0 | 21-53-22 | D05506J | 17 | | | TB0192X | A004 | BJ | | ALL | |
| 018 | 24 | | PK | | 4-6 | 21-58-14 | D05506J | 9 | | | TB0274X | C012 | BJ | | ALL | |
| 019 | 24 | | PK | | 1-7 | 29-11-22 | D05506J | 25 | | | D04934J | 5 | | | ALL | |
| 021 | 22 | | PA | | 1-7 | 29-11-22 | D05506J | 26 | | | D04934J | 6 | | | ALL | |
| 023 | 24 | | PK | | 1-7 | 21-53-22 | D05506J | 30 | | | D04934J | 12 | | | ALL | |
| 024 | 24 | | PK | | 1-7 | 21-53-22 | D05506J | 31 | | | D04934J | 13 | | | ALL | |
| 025 | 24 | | PK | | 1-7 | 21-53-22 | D05506J | 32 | | | D04934J | 10 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 28

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0188 | 286T0188 | | | | P37-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 026 | 24 | | PK | | 1-7 | 21-53-22 | D05506J | | 33 | | | | D04934J | 11 | | ALL |
| 027 | 24 | | PK | | 1-7 | 21-53-22 | D05506J | | 34 | | | | D04934J | 14 | | ALL |
| 028 | 24 | | PK | | 1-7 | 21-53-22 | D05506J | | 35 | | | | D04934J | 16 | | ALL |
| 036 | 24 | | PK | | 1-7 | 29-11-22 | D05506J | | 27 | | | | D04934J | 7 | | ALL |
| 037 | 22 | | PA | | 1-7 | 29-11-22 | D05506J | | 28 | | | | D04934J | 8 | | ALL |
| 038 | 24 | | PK | | 4-0 | 21-58-11 | D05506J | | 38 | | | | TB0192X | C001 | BJ | ALL |
| 039 | 24 | | PK | | 9-3 | 21-61-41 | D05506J | | 36 | | | | TB0082Z | 13 | BJ | 050-099 |
| 039 | 24 | | PK | | 9-3 | 21-61-41 | TB0082Z | | 13 | BJ | | | D05506J | 36 | | 150-199, 275-299 |
| 042 | 24 | | PK | | 9-3 | 21-61-41 | D05506J | | 44 | | | | TB0082Y | A001 | BJ | ALL |
| 043 | 22 | | PQ | AE | 3-4 | 28-31-12 | D05372J | | 1 | | | | TB0320Y | C012 | BJ | 050 |
| 043 | 22 | | PQ | AE | 4-6 | 28-31-12 | D05372J | | 1 | | | | TB0212Y | A014 | BJ | 051-099, 155-199, 277-299 |
| 043 | 22 | | PQ | AE | 3-3 | 28-31-12 | D05372J | | 1 | | | | TB0304D | A037 | 2 | 276 |
| 043Z | | | | AE | 0-0 | 28-31-12 | D05372J | | DED | | | | TB0320Y | DED | | 050 |
| 043Z | | | | AE | 0-0 | 28-31-12 | D05372J | | DED | | | | TB0212Y | DED | | 051-099, 155-199, 277-299 |
| 043Z | | | | AE | 0-0 | 28-31-12 | D05372J | | DED | | | | TB0304D | DED | | 276 |
| 049 | 22 | | PQ | AF | 4-6 | 28-42-13 | D05372J | | 20 | | | | TB0210X | D009 | BJ | 050-099, 155-199, 276-299 |
| 049Z | | | | AF | 0-0 | 28-42-13 | D05372J | | DED | | | | TB0210X | DED | | 050-099, 155-199, 276-299 |
| 060 | 24 | | PK | | 1-6 | 27-18-11 | D05330J | | 17 | | | | D05372J | 8 | | 050-099, 150-154, 162-165, 275-276 |
| 061 | 24 | | PK | | 1-6 | 27-18-11 | D05330J | | 18 | | | | D05372J | 7 | | 050-099, 150-154, 162-165, 275-276 |
| 062 | 24 | | PK | | 1-6 | 27-18-11 | D05330J | | 14 | | | | D05372J | 4 | | 050-099, 150-154, 162-165, 275-276 |
| 063 | 24 | | PK | | 1-6 | 27-18-11 | D05330J | | 15 | | | | D05372J | 3 | | 050-099, 150-154, 162-165, 275-276 |
| 068 | 24 | | PK | | 4-0 | 36-11-41 | D05506J | | 47 | | | | TB0190X | C013 | BJ | ALL |
| 073 | 24 | | PK | | 20-0 | 28-42-12 | D05372J | | 5 | | | | TB0212Z | 19 | BJ | ALL |
| 074 | 22 | | X1 | EA | 20-0 | 28-42-12 | D05330J | | 22 | | | | TB0212Z | 19 | BJ | ALL |
| 074Z | | | | EA | 0-0 | 28-42-12 | D05330J | | DED | | | | TB0212Z | DED | | ALL |
| 075 | 22 | | PA | | 20-0 | 28-42-12 | D05506J | | 3 | | | | TB0212Z | 19 | BJ | ALL |
| 076R | 22 | | PH | | 3-0 | 26-18-21 | D05506J | | 41 | | | | TB0304X | D004 | BJ | ALL |
| 081 | 24 | | PK | | 3-10 | 22-41-11 | D05330J | | 1 | | | | TB0192Z | 17 | BJ | ALL |
| 094 | 24 | | PK | | 3-3 | 30-21-11 | TB0320X | | A001 | BJ | | | D05506J | 60 | | 050-099 |
| 094 | 24 | | PK | | 3-3 | 30-21-11 | D05506J | | 60 | | | | TB0320X | A001 | BJ | 150-199 |
| 100R | 22 | | PH | | 1-7 | 26-18-21 | D05506J | | 55 | | | | D04934J | 15 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 29

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0188 | 286T0188 | | | P37-L2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 107 | 22 | | PA | 3-3 | 28-42-11 | D05330J | | 21 | | | | | TB0304Y | C013 | BJ | | 050-099 |
| 107 | 22 | | PA | 4-0 | 28-42-11 | D05330J | | 21 | | | | | TB0304Y | C013 | BJ | | 150-199, 275-299 |
| 108 | 24 | | PK | 3-3 | 28-42-11 | D05372J | | 11 | | | | | TB0304Y | C013 | BJ | | ALL |
| 109 | 24 | | PK | 4-7 | 78-36-11 | D05372J | | 2 | | | | | TB0274D | C014 | 2 | | ALL |
| 110 | 22 | | PA | 4-6 | 78-36-11 | D05330J | | 2 | | | | | TB0274D | C014 | 2 | | ALL |
| 111 | 22 | | PA | 1-6 | 78-36-11 | TB0274D | | A014 | 2 | | | | TB0274Y | A011 | BJ | | 050-099 |
| 111 | 22 | | PA | 2-0 | 78-36-11 | TB0274D | | A014 | 2 | | | | TB0274Y | A011 | BJ | | 150-199, 275-299 |
| 112 | 22 | | PA | 4-9 | 78-36-11 | D04934J | | 26 | | | | | TB0274Y | A011 | BJ | | ALL |
| 114 | 24 | | PK | 4-0 | 21-26-11 | D05506J | | 4 | | | | | TB0190X | D013 | BJ | | ALL |
| 11A | 24 | | PK | 4-6 | 21-43-11 | D05506J | | 57 | | | | | TB0210X | A020 | BJ | | 050-099, 275-299 |
| 11A | 24 | | PK | 4-6 | 21-43-11 | TB0210X | | A020 | BJ | | | | D05506J | 57 | | | 150-199 |
| 11B | 24 | | PK | 4-6 | 21-43-11 | D05506J | | 58 | | | | | TB0210X | B020 | BJ | | 050-099, 275-299 |
| 11B | 24 | | PK | 4-6 | 21-43-11 | TB0210X | | B020 | BJ | | | | D05506J | 58 | | | 150-199 |
| 11C | 24 | | PK | 4-6 | 21-43-11 | D05506J | | 59 | | | | | TB0210X | C020 | BJ | | 050-099 |
| 11C | 24 | | PK | 4-6 | 21-43-11 | TB0210X | | C020 | BJ | | | | D05506J | 59 | | | 150-199, 275-299 |
| 11D | 22 | | PA | 8-8 | 21-28-11 | D05506J | | 12 | | | | | TB0314X | A009 | BJ | | 050-099 |
| 11D | 22 | | PA | 8-8 | 21-28-11 | TB0314X | | A009 | BJ | | | | D05506J | 12 | | | 150-199, 275-276 |
| 11E | 22 | | PA | 8-8 | 21-28-11 | D05506J | | 22 | | | | | TB0314X | B009 | BJ | | 050-099 |
| 11E | 22 | | PA | 8-8 | 21-28-11 | TB0314X | | B009 | BJ | | | | D05506J | 22 | | | 150-199, 275-276 |
| 11F | 24 | | PK | 8-8 | 21-28-11 | D05506J | | 56 | | | | | TB0314Z | 7 | BJ | | 050-099, 155-199, 275-299 |
| 11F | 24 | | PK | 3-0 | 21-28-11 | D05506J | | 56 | | | | | TB0304Y | C024 | BJ | | 150 |
| 11F | 24 | | PK | 3-0 | 21-28-11 | D05506J | | 56 | | | | | TB0304Y | CAP | Y | | 151-154 |
| 11G | 22 | | PA | 4-6 | 32-45-11 | D05506J | | 20 | | | | | TB0274X | C013 | BJ | | 275-299 |
| 11H | 22 | | PA | 4-6 | 32-45-11 | D05506J | | 24 | | | | | TB0274X | B013 | BJ | | 275-299 |
| 121 | 18 | | PA | 3-3 | 33-44-21 | D05330J | | 19 | DL | | | | TB0304G | 31 | 2 | | 050-099 |
| 121 | 18 | | PA | 3-0 | 33-44-21 | D05330J | | 19 | DL | | | | TB0304G | 31 | 2 | | 150-199, 275-299 |
| 122 | 22 | | PQ | C | 3-3 | 29-11-22 | D05330J | | 3 | | | | TB0304X | C006 | BJ | | ALL |
| 122Z | | | | C | 0-0 | 29-11-22 | D05330J | | DED | | | | TB0304X | DED | | | ALL |
| 124 | 24 | | PK | | 4-6 | 36-11-41 | D05506J | | 42 | | | | TB0274Y | C011 | BJ | | ALL |
| 125 | 24 | | PK | | 4-0 | 36-11-41 | D05506J | | 43 | | | | TB0192Y | A006 | BJ | | ALL |
| 126 | 24 | | PV | F | 4-6 | 29-11-12 | D05506J | | 14 | | | | TB0274D | A020 | 2 | | ALL |
| 126Z | | | | F | 0-0 | 29-11-12 | D05506J | | DED | | | | TB0274D | DED | | | ALL |
| 127 | 24 | | PK | | 4-6 | 29-11-22 | D05506J | | 15 | | | | TB0274D | A021 | 2 | | ALL |
| 130 | 24 | | PK | | 4-6 | 27-51-61 | D05372J | | 6 | | | | TB0212Y | A010 | BJ | | ALL |
| 131 | 24 | | PK | | 4-1 | 27-51-61 | D04934J | | 25 | | | | TB0192X | D005 | BJ | | ALL |
| 132 | 24 | | PK | | 4-1 | 27-51-61 | D04934J | | 31 | | | | TB0192X | C008 | BJ | | ALL |
| 133 | 24 | | PK | | 4-8 | 27-51-61 | D04934J | | 9 | | | | TB0212Y | A010 | BJ | | 050-099 |
| 135 | 24 | | PK | | 4-6 | 36-11-41 | D05506J | | 6 | | | | TB0274D | C031 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0180

Page 30

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0188 | 286T0188 | | | | P37-L2-INTEGRATION (continued) | | | | | | | | | | | |
| 136 | 24 | | PK | | 4-6 | 36-11-41 | D05506J | | 5 | | TB0274Y | A034 | BJ | | | ALL |
| 139 | 24 | | PK | | 4-0 | 21-45-21 | D05506J | | 37 | | TB0192X | A001 | BJ | | | ALL |
| 201B | 22 | | PB | A | 3-3 | 27-51-41 | D05330J | | 7 | | TB0304X | B006 | BJ | | | ALL |
| 201R | 22 | | PB | A | 0-0 | 27-51-41 | D05330J | | 8 | | TB0304X | A006 | BJ | | | ALL |
| 203B | 24 | | PL | D | 1-7 | 21-51-12 | D05506J | | 53 | | D04934J | 18 | | | | ALL |
| 203R | 24 | | PL | D | 0-0 | 21-51-12 | D05506J | | 54 | | D04934J | 17 | | | | ALL |
| 206B | 22 | | PB | G | 1-7 | 21-51-23 | D04934J | | 4 | | D05506J | 48 | | | | ALL |
| 206R | 22 | | PB | G | 0-0 | 21-51-23 | D04934J | | 20 | | D05506J | 49 | | | | ALL |
| 207B | 22 | | PB | H | 1-7 | 21-51-23 | D04934J | | 23 | | D05506J | 18 | | | | ALL |
| 207R | 22 | | PB | H | 0-0 | 21-51-23 | D04934J | | 24 | | D05506J | 19 | | | | ALL |
| 270B | 20 | | PR | AD | 3-3 | 32-45-12 | D05506J | | 51 | | TB0320X | D035 | BJ | | | 275-299 |
| 270R | 20 | | PR | AD | 0-0 | 32-45-12 | D05506J | | 50 | | TB0320X | C035 | BJ | | | 275-299 |
| 270Z | | | | AD | 0-0 | 32-45-12 | D05506J | | 29 | | TB0320X | A036 | BJ | | | 275-299 |
| 271B | 20 | | PR | AB | 3-3 | 32-45-12 | D05506J | | 61 | | TB0320X | C036 | BJ | | | 275-299 |
| 271R | 20 | | PR | AB | 0-0 | 32-45-12 | D05506J | | 60 | | TB0320X | B036 | BJ | | | 275-299 |
| 271Z | | | | AB | 0-0 | 32-45-12 | D05506J | | 39 | | TB0320X | D036 | BJ | | | 275-299 |
| 401B | 24 | | PN | B | 3-3 | 27-51-41 | D05330J | | 9 | | TB0304X | D005 | BJ | | | ALL |
| 401G | 24 | | PN | B | 0-0 | 27-51-41 | D05330J | | 12 | | TB0304X | A005 | BJ | | | ALL |
| 401R | 24 | | PN | B | 0-0 | 27-51-41 | D05330J | | 10 | | TB0304X | C005 | BJ | | | ALL |
| 401Y | 24 | | PN | B | 0-0 | 27-51-41 | D05330J | | 11 | | TB0304X | B005 | BJ | | | ALL |
| 70A | 24 | | PK | | 4-6 | 21-61-51 | D05506J | | 8 | | TB0274Y | C029 | BJ | | | ALL |
| 70C | 20 | | PA | | 4-6 | 29-11-14 | D05506J | | 23 | | TB0274D | C041 | 2 | | | ALL |
| 70D | 20 | | PA | | 4-0 | 29-11-14 | D05506J | | 45 | | TB0192X | B009 | BJ | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0180
Page 31 End
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION | | | | | | | | | | | | | | |
| 004 | 24 | | PK | | 20-0 | 28-22-12 | TB0212Z | | 17 | | BJ | | D04284J | | 12 | | | ALL |
| 005 | 20 | | PA | | 3-0 | 73-21-19 | D03692 | | 10 | | | | GD00014 | | D.. | 2 | | ALL |
| 011 | 22 | | PA | | 6-0 | 78-34-21 | D05326J | | 53 | | | | D20104 | | B2 | | | 050-099, 150-156, 162-166, 275-276 |
| 011 | 22 | | PA | | 12-0 | 78-34-21 | D05326J | | 53 | | | | D20104 | | B2 | | | 157, 167-199, 277-299 |
| 012 | 24 | | PK | | 3-0 | 31-41-13 | D05328J | | 9 | | | | D05316J | | 27 | | | 050-099 |
| 012 | 24 | | PK | | 3-0 | 31-41-13 | D05316J | | 27 | | | | D05328J | | 9 | | | 150-199, 275-299 |
| 013 | 20 | | PQ | HL | 3-0 | 78-34-21 | D03728 | | C1 | | | | TB0084Z | | 3 | BJ | | 050-099, 150-156, 162-166, 275-276 |
| 013 | 20 | | PQ | HL | 6-0 | 78-34-21 | D03728 | | C1 | | | | TB0084Z | | 3 | BJ | | 157, 167-199, 277-299 |
| 013Z | | | | HL | 0-0 | 78-34-21 | D03728 | | DED | | | | TB0084Z | | | | HK | ALL |
| 014 | 24 | | PK | | 3-0 | 32-09-12 | D03728 | | X1 | | | | TB0084Z | | 9 | BJ | | ALL |
| 015 | 24 | | PK | | 3-0 | 32-09-12 | D03728 | | X2 | | | | TB0084Z | | 4 | BJ | | ALL |
| 016 | 20 | | PA | | 2-0 | 36-11-21 | D03668 | | A3 | | | | GD00015 | | D.. | 2 | | ALL |
| 017 | 24 | | PK | | 3-0 | 36-11-21 | D03668 | | X1 | | | | TB0084Y | | C008 | BJ | | ALL |
| 018 | 20 | | PA | | 2-0 | 36-11-21 | D03666 | | A3 | | | | GD00015 | | D.. | 2 | | ALL |
| 019 | 24 | | PK | | 3-0 | 36-11-21 | D03666 | | X1 | | | | TB0084Y | | C008 | BJ | | ALL |
| 01A | 20 | | UA | | 1-6 | 31-31-12 | GD00013 | | S.. | 2 | | | D01644 | | | | FE | 050-099 |
| 01A | 20 | | UA | | 2-0 | 31-31-12 | GD00013 | | S.. | 2 | | | D01644 | | | | FE | 150-199, 275-299 |
| 01B | 20 | | UA | | 1-6 | 31-31-12 | GD00013 | | S.. | 2 | | | D01644 | | | | FF | 050-099 |
| 01B | 20 | | UA | | 2-0 | 31-31-12 | GD00013 | | S.. | 2 | | | D01644 | | | | FF | 150-199, 275-299 |
| 01C | 20 | | UA | | 1-6 | 31-31-12 | GD00013 | | S.. | 2 | | | D01644 | | | | FG | 050-099 |
| 01C | 20 | | UA | | 2-0 | 31-31-12 | GD00013 | | S.. | 2 | | | D01644 | | | | FG | 150-199, 275-299 |
| 01D | 22 | | PA | | 6-0 | 31-31-11 | D05435J | | 24 | | | | TB0210Y | | A016 | BJ | | ALL |
| 01E | 24 | | PK | | 7-0 | 34-12-22 | D05437J | | 7 | | | | D03692 | | 1 | | | ALL |
| 01F | 24 | | PK | | 3-0 | 29-32-11 | D05068J | | 19 | | | | D05374J | | 17 | | | ALL |
| 01G | 24 | | PK | | 3-0 | 29-32-11 | D05068J | | 20 | | | | D05374J | | 18 | | | ALL |
| 01H | 24 | | PK | | 3-0 | 36-11-21 | D05352J | | 43 | | | | D04004J | | 12 | | | ALL |
| 01J | 24 | | PK | | 9-0 | 31-41-13 | D05328J | | 8 | | | | D03688 | | 10 | | | ALL |
| 01K | 20 | | PA | | 3-0 | 36-11-52 | D01724 | | C2 | | | | GD00001 | | D.. | 2 | | ALL |
| 01L | 20 | | PA | | 2-0 | 31-41-13 | GD00015 | | D.. | 2 | | | D03688 | | 11 | | | ALL |
| 01M | 24 | | PK | | 8-0 | 34-61-24 | D03684 | | 11 | | | | D05435J | | 21 | | | ALL |
| 01N | 22 | | PQ | BQ | 4-0 | 29-11-22 | D04346J | | 41 | | | | TB0304X | | C006 | BJ | | ALL |
| 01NZ | | | | BQ | 0-0 | 29-11-22 | D04346J | | DED | | | | TB0304X | | DED | | | ALL |
| 01P | 22 | | PA | | 5-0 | 21-26-21 | D01006 | | C1 | | | | TB0192X | | C002 | BJ | | ALL |
| 01Q | 24 | | PK | | 3-0 | 34-12-22 | D05435J | | 5 | | | | D05437J | | 33 | | | ALL |
| 01S | 24 | | PK | | 3-0 | 34-12-22 | D05435J | | 6 | | | | D05437J | | 34 | | | ALL |
| 01T | 20 | | PA | | 3-0 | 21-26-21 | D01006 | | X2 | | | | GD00003 | | D.. | 2 | | ALL |
| 01U | 24 | | PK | | 3-0 | 21-25-21 | SP02250 | | | | W | | TB0210Y | | C015 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 1

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 01V | 20 | PA | | | 5-0 | 30-71-24 | D03748 | | B2 | | TB0210Z | 11 | BJ | | 050-099 |
| 01V | 20 | PA | | | 6-0 | 30-71-24 | TB0210Z | | 11 | BJ | D03748 | | B2 | | 150-199 |
| 01W | 24 | PK | | | 4-0 | 21-25-21 | SP02252 | | | W | TB0192Y | A013 | BJ | | ALL |
| 01X | 24 | PK | | | 6-0 | 21-25-21 | D05374J | | 2 | | TB0210Y | C015 | BJ | | ALL |
| 01Y | 20 | PA | | | 5-0 | 30-71-24 | D03748 | | B1 | | TB0210Y | A004 | BJ | | 050 |
| 01Y | 20 | PA | | | 5-0 | 30-71-24 | D03748 | | B1 | | TB0320Y | A011 | BJ | | 051-099 |
| 01Y | 20 | PA | | | 6-0 | 30-71-24 | TB0210Y | A004 | BJ | | D03748 | | B1 | | 150-154 |
| 01Y | 20 | PA | | | 6-0 | 30-71-24 | TB0320Y | A011 | BJ | | D03748 | | B1 | | 155-199 |
| 01Z | 20 | PA | | | 6-0 | 21-25-21 | SP02254 | | | W | GDX0013 | | D.. | 2 | ALL |
| 020 | 24 | PK | | | 9-0 | 32-09-12 | D05316J | | 4 | | TB0082Y | A006 | BJ | | ALL |
| 021 | 24 | PK | | | 10-0 | 32-09-12 | D05374J | | 34 | | TB0082Y | A006 | BJ | | ALL |
| 022 | 24 | PK | | | 3-0 | 32-09-12 | D03688 | | 12 | | TB0084Z | | 4 | BJ | ALL |
| 023 | 24 | PK | | | 3-0 | 32-09-12 | D03688 | | 6 | | TB0084Z | | 9 | BJ | ALL |
| 024 | 20 | PA | | | 2-0 | 22-14-31 | D03686 | | 2 | | GDX0015 | | D.. | 2 | ALL |
| 025 | 22 | PA | | | 3-0 | 22-14-31 | D03686 | | 1 | | TB0084Y | A007 | BJ | | ALL |
| 026 | 20 | PA | | | 2-0 | 22-14-31 | D03686 | | 4 | | GDX0015 | | D.. | 2 | ALL |
| 027 | 22 | PA | | | 3-0 | 22-14-31 | D03686 | | 5 | | TB0084Y | A007 | BJ | | ALL |
| 028 | 20 | PA | | | 2-0 | 22-14-31 | D03686 | | 8 | | GDX0015 | | D.. | 2 | 050-099, 275-299 |
| 028 | 20 | PA | | | 4-0 | 22-14-31 | D03686 | | 8 | | GDX0015 | | D.. | 2 | 150-199 |
| 029 | 22 | PA | | | 3-0 | 22-14-31 | D03686 | | 7 | | TB0084Y | C007 | BJ | | ALL |
| 02A | 16 | PA | | | 6-0 | 33-45-11 | D03174 | | A3 | | TB0190F | A009 | 2 | | 050-099 |
| 02A | 16 | PA | | | 7-0 | 33-45-11 | D03174 | | A3 | | TB0190F | A009 | 2 | | 150-199, 275-299 |
| 02B | 16 | PA | | | 8-0 | 33-45-11 | D03174 | | A1 | | D04962J | | 27 | | ALL |
| 02C | 16 | PA | | | 6-0 | 33-45-11 | D03174 | | B3 | | TB0190F | C009 | 2 | | ALL |
| 02D | 16 | PA | | | 9-0 | 33-45-11 | D04962J | | 28 | | TB0082G | | 9 | 2 | 050-099 |
| 02D | 16 | PA | | | 9-0 | 33-45-11 | TB0082G | | 9 | 2 | D04962J | | 28 | | 150-199, 275-299 |
| 02E | 16 | PA | | | 7-0 | 33-45-11 | D03174 | | B1 | | TB0082G | | 9 | 2 | 050-099 |
| 02E | 16 | PA | | | 8-0 | 33-45-11 | D03174 | | B1 | | TB0082G | | 9 | 2 | 150-199, 275-299 |
| 02F | 22 | PA | | | 7-0 | 33-45-11 | D03174 | | X1 | | TB0082G | | 9 | 2 | 050-099 |
| 02F | 22 | PA | | | 8-0 | 33-45-11 | D03174 | | X1 | | TB0082G | | 9 | 2 | 150-199, 275-299 |
| 02G | 22 | PA | | | 3-0 | 33-45-11 | D03174 | | X2 | | D03690 | | 8 | | ALL |
| 02H | 22 | PA | | | 7-0 | 33-45-11 | D03176 | | X1 | | TB0082G | | 9 | 2 | 050-099 |
| 02H | 22 | PA | | | 9-0 | 33-45-11 | TB0082G | | 9 | 2 | D03176 | | X1 | | 150-199, 275-299 |
| 02J | 22 | PA | | | 8-0 | 33-45-11 | D03176 | | X2 | | D04340J | | 4 | | ALL |
| 02K | 20 | PA | | | 3-0 | 33-45-11 | D03690 | | 7 | | GDX0007 | | A.. | 2 | ALL |
| 02L | 16 | PA | | | 2-0 | 33-45-11 | D03174 | | A2 | | D03176 | | A2 | | ALL |
| 02M | 16 | PA | | | 2-0 | 33-45-11 | D03174 | | B2 | | D03176 | | B2 | | ALL |
| 02N | 16 | PA | | | 9-0 | 33-45-11 | D03176 | | A1 | | D05352J | | 16 | FM | ALL |
| 02P | 16 | PA | | | 9-0 | 33-45-11 | D03176 | | B1 | | D05352J | | 17 | FM | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 2

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 02Q | 24 | | PK | 8-0 | 21-26-11 | D10078 | | 9 | | | | | D12240 | 14 | | | 050-099, 155-199, 276-299 |
| 02Q | 24 | | PK | 7-0 | 21-26-11 | D10078 | | 9 | | | | | D04646J | 6 | | | 150-154, 275 |
| 02R | 24 | | PK | 8-0 | 21-26-11 | D10078 | | 8 | | | | | D12240 | 9 | | | 050-099, 155-199, 276-299 |
| 02R | 24 | | PV | 7-0 | 21-26-11 | D10078 | | 8 | | | | | TB0190X | D013 | BJ | | 150-154, 275 |
| 02RZ | | | C | 0-0 | 21-26-11 | D10078 | | DED | | | | | TB0190X | DED | | | 150-154, 275 |
| 02S | 20 | | PA | 11-0 | 21-26-11 | D10078 | | 11 | | | | | D10724 | A1 | | | ALL |
| 02T | 20 | | PA | 3-0 | 21-26-11 | D10078 | | 7 | | | | | GDX0001 | D.. | 2 | | 050-099, 155-199, 276-299 |
| 02T | 20 | | PQ | 3-0 | 21-26-11 | D10078 | | 7 | | | | | GDX0001 | D.. | 2 | | 150-154, 275 |
| 02TZ | | | AG | 0-0 | 21-26-11 | D10078 | | DED | | | | | GDX0001 | DED | | | 150-154, 275 |
| 02U | 24 | | PK | 8-0 | 21-58-11 | D06260J | | 16 | | | | | D10074 | 12 | | | ALL |
| 02V | 24 | | PK | 7-0 | 21-58-11 | D10074 | | 4 | | | | | D05266J | 21 | | | ALL |
| 02Y | 24 | | PK | 7-0 | 21-61-21 | D06076J | | 4 | | | | | TB0254Y | C003 | BJ | | ALL |
| 02Z | 24 | | PK | 7-0 | 21-61-31 | D06076J | | 5 | | | | | TB0254Y | A005 | BJ | | ALL |
| 030 | 20 | | PA | 2-0 | 22-14-31 | D03686 | | 10 | | | | | GDX0015 | D.. | 2 | | ALL |
| 031 | 22 | | PA | 3-0 | 22-14-31 | D03686 | | 11 | | | | | TB0084Y | C007 | BJ | | ALL |
| 032 | 24 | | PK | 3-0 | 32-09-12 | D03686 | | 12 | | | | | TB0084Z | 4 | BJ | | ALL |
| 033 | 24 | | PK | 3-0 | 32-09-12 | D03686 | | 6 | | | | | TB0084Z | 10 | BJ | | ALL |
| 034 | 24 | | PK | 7-0 | 32-09-12 | D03692 | | 6 | | | | | TB0084Z | 9 | BJ | | ALL |
| 035 | 24 | | PK | 3-0 | 32-09-12 | D03692 | | 12 | | | | | TB0082Z | 7 | BJ | | ALL |
| 036 | 24 | | PK | 3-0 | 36-11-52 | D05068J | | 27 | | | | | D05768J | 6 | | | ALL |
| 037 | 18 | | PA | 3-0 | SPARE | D05068J | | 28 | DK | | | | D05768J | CAP | Y | | 150-154, 275 |
| 038 | 24 | | PK | 3-0 | 36-11-52 | D05068J | | 29 | | | | | D05768J | 8 | | | ALL |
| 039 | 24 | | PK | 3-0 | 36-11-52 | D05068J | | 31 | | | | | D05768J | 10 | | | ALL |
| 03A | 24 | | PK | 5-0 | 75-23-11 | D10344 | | A3 | | | | | D05326J | 1 | | | ALL |
| 03B | 24 | | PK | 6-0 | 75-23-11 | D10344 | | A2 | | | | | D05374J | 25 | | | ALL |
| 03C | 24 | | PK | 5-0 | 75-23-11 | D10344 | | A1 | | | | | D05326J | 15 | | | ALL |
| 03D | 24 | | PK | 5-0 | 75-23-11 | D10344 | | X1 | | | | | D05326J | 16 | | | ALL |
| 03E | 24 | | PK | 5-0 | 75-23-11 | D10344 | | X2 | | | | | D05326J | 17 | | | ALL |
| 03G | 24 | | PK | 3-0 | 21-44-11 | D05374J | | 38 | | | | | TB0304Y | A011 | BJ | | ALL |
| 03H | 24 | | PK | 4-0 | 21-51-13 | D05612J | | 14 | | | | | D05352J | 29 | | | ALL |
| 03K | 24 | | PK | 4-0 | 21-51-21 | D06260J | | 23 | | | | | TB0304Y | A012 | BJ | | ALL |
| 03L | 24 | | PK | 4-0 | 21-51-21 | D04004J | | 6 | | | | | TB0304Y | A012 | BJ | | ALL |
| 03M | 24 | | PK | 3-0 | 21-61-21 | D10150 | | 7 | | | | | TB0088D | C001 | 2 | | ALL |
| 03N | 24 | | PK | 3-0 | 21-61-21 | D10150 | | 3 | | | | | TB0088D | A001 | 2 | | ALL |
| 03P | 24 | | PK | 3-0 | 21-61-31 | D10156 | | 7 | | | | | TB0088D | C002 | 2 | | ALL |
| 03Q | 24 | | PK | 3-0 | 21-61-31 | D10156 | | 3 | | | | | TB0088D | A002 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 3

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 03S | 24 | PV | | BU | 5-0 | 21-58-11 | D04004J | | 21 | | TB0212Y | C008 | BJ | | ALL |
| 03SZ | | | | BU | 0-0 | 21-58-11 | D04004J | | DED | | TB0212Y | DED | | | ALL |
| 03T | 24 | PK | | | 7-0 | 21-58-11 | D10074 | | 6 | | TB0212Y | C008 | BJ | | ALL |
| 03X | 24 | PV | | BW | 3-0 | 21-58-11 | D04004J | | 20 | | D06260J | 13 | | | ALL |
| 03XZ | | | | BW | 0-0 | 21-58-11 | D04004J | | DED | | D06260J | DED | | | ALL |
| 03Y | 20 | PA | | | 3-0 | 21-58-11 | D10074 | | 7 | | GD00002 | D.. | 2 | | ALL |
| 03Z | 20 | PA | | | 3-0 | 21-58-11 | D10074 | | 5 | | GD00002 | D.. | 2 | | ALL |
| 040 | 22 | PA | | | 10-0 | 36-11-52 | TB0314Y | | C003 | BJ | D05768J | 11 | | | ALL |
| 041 | 22 | PA | | | 10-0 | 36-11-52 | TB0314Y | | A003 | BJ | D05768J | 12 | | | 050-099, 150-156, 162-166, 275-299 |
| 041 | 22 | PA | | | 10-0 | 36-11-52 | D05768J | | 12 | | TB0314Y | A003 | BJ | | 157, 167-199 |
| 042 | 24 | PK | | | 3-0 | 36-11-52 | D05068J | | 34 | | D05768J | 13 | | | ALL |
| 044 | 24 | PK | | | 3-0 | 36-11-62 | D04346J | | 12 | | D05768J | 15 | | | ALL |
| 045 | 24 | PK | | | 3-0 | 36-11-62 | D04346J | | 13 | | D05768J | 16 | | | ALL |
| 046 | 20 | PA | | | 6-0 | 21-25-21 | SP01602 | | | W | GD00013 | D.. | 2 | | ALL |
| 047 | 24 | PK | | | 3-0 | 21-25-21 | SP01600 | | | W | TB0192Y | C012 | BJ | | ALL |
| 048 | 22 | PA | | | 7-0 | 36-11-62 | D01724 | | B3 | | D11900 | 7 | | | 050-099, 150-154, 162-165 |
| 048 | 22 | PA | | | 8-0 | 36-11-62 | D01724 | | B3 | | D11900 | 7 | | | 155-156, 166 |
| 048 | 22 | PA | | | 10-0 | 36-11-62 | D11900 | | 7 | | D01724 | B3 | | | 275-276 |
| 049 | 20 | PA | | | 8-0 | 36-11-62 | TB0254G | | 13 | 2 | D05768J | 18 | | | 050-099, 156, 166 |
| 049 | 20 | PA | | | 9-0 | 36-11-62 | TB0254G | | 13 | 2 | D05768J | 18 | | | 150-154, 162-165 |
| 049 | 20 | PA | | | 10-0 | 36-11-62 | TB0254G | | 13 | 2 | D05768J | 18 | | | 155 |
| 049 | 20 | PA | | | 10-0 | 36-11-62 | TB0314Y | | C004 | BJ | D05768J | 18 | | | 157, 167-199, 277-299 |
| 049 | 20 | PA | | | 3-0 | 36-11-62 | TB0254G | | 13 | 2 | D05768J | 18 | | | 275-276 |
| 04A | 20 | PA | | | 3-0 | 21-58-11 | D10074 | | 1 | | GD00002 | D.. | 2 | | ALL |
| 04B | 24 | PK | | | 7-0 | 21-58-11 | D10074 | | 2 | | D05266J | 20 | | | ALL |
| 04D | 20 | PA | | | 3-0 | 21-58-14 | D10078 | | 5 | | GD00001 | D.. | 2 | | ALL |
| 04E | 24 | PK | | | 4-0 | 21-58-14 | D10078 | | 6 | | TB0254Y | A009 | BJ | | 050-099, 155-199, 276-299 |
| 04E | 24 | PK | | | 7-0 | 21-58-14 | D10078 | | 6 | | D05612J | 5 | | | 150-154, 275 |
| 04F | 24 | PK | | | 7-0 | 21-58-14 | D10078 | | 12 | | D05612J | 17 | | | ALL |
| 04G | 24 | PK | | | 8-0 | 21-58-14 | D10078 | | 4 | | D12242 | 2 | | | 050-099, 155-199, 276-299 |
| 04G | 24 | PV | | Z | 7-0 | 21-58-14 | D10078 | | 4 | | TB0274X | C012 | BJ | | 150-154, 275 |
| 04GZ | | | | Z | 0-0 | 21-58-14 | D10078 | | DED | | TB0274X | DED | | | 150-154, 275 |
| 04P | 22 | PA | | | 7-0 | 21-61-11 | D05374J | | 4 | | TB0192Y | A012 | BJ | | ALL |
| 04Q | 20 | PA | | | 2-0 | 21-61-21 | D10148 | | 6 | | GD00001 | D.. | 2 | | 050-099, 277-299 |
| 04Q | 20 | PA | | | 2-0 | 21-61-21 | D10148 | | 6 | | GD00001 | D.. | 2 | * | 150-199, 275-276 |

WIRE LIST
D280T132

91-21-11
Section W0190
Page 4
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 04R | 20 | | PA | 2-0 | 21-61-21 | D10148 | | | | 2 | | | GDX0001 | D.. | 2 | | 050-099, 277-299 |
| 04R | 20 | | PA | 2-0 | 21-61-21 | D10148 | | | | 2 | | | GDX0001 | D.. | 2 | * | 150-199, 275-276 |
| 04S | 24 | | PK | 2-0 | 21-61-21 | D10148 | | | | 1 | | | D10150 | | 2 | | ALL |
| 04T | 22 | | PA | 6-0 | 21-61-21 | D10148 | | | | 4 | | | TB0210Z | 12 | BJ | | ALL |
| 04U | 24 | | PK | 3-0 | 21-61-21 | D10148 | | | | 7 | | | TB0254Z | 7 | BJ | | ALL |
| 04V | 22 | | PA | 6-0 | 21-61-21 | D10150 | | | | 1 | | | TB0210Z | 12 | BJ | | ALL |
| 04W | 24 | | PK | 3-0 | 21-61-21 | D10150 | | | | 5 | | | TB0254Y | C003 | BJ | | ALL |
| 04X | 24 | | PK | 10-0 | 21-61-21 | TB0088D | | | C001 | 2 | | | TB0320Y | A033 | BJ | | 050-099 |
| 04X | 24 | | PK | 8-0 | 21-61-21 | TB0088D | | | C001 | 2 | | | TB0320Y | A033 | BJ | | 150-199 |
| 04X | 24 | | PK | 2-0 | 21-61-21 | TB0088D | | | C001 | 2 | | | TB0320Y | A033 | BJ | | 275-299 |
| 04Z | 24 | | PK | 6-0 | 21-61-21 | D05374J | | | | 5 | | | TB0210Z | 12 | BJ | | ALL |
| 050 | 24 | | PK | 3-0 | 32-09-12 | D03714 | | | | X1 | | | TB0084Z | 9 | BJ | | ALL |
| 051 | 24 | | PK | 3-0 | 32-09-12 | D03714 | | | | X2 | | | TB0084Z | 4 | BJ | | ALL |
| 052 | 24 | | PK | 2-0 | 32-09-12 | TB0084Z | | | | 10 | BJ | | TB0084Z | 9 | BJ | | ALL |
| 053 | 24 | | PK | 2-0 | 32-09-12 | TB0084Z | | | | 13 | BJ | | TB0084Z | 10 | BJ | | ALL |
| 054 | 24 | | PK | 9-0 | 32-09-12 | D05768J | | | | 49 | | | TB0084Z | 4 | BJ | | ALL |
| 055 | 24 | | PK | 10-0 | 32-09-12 | D05374J | | | | 33 | | | TB0084Y | C001 | BJ | | ALL |
| 056 | 24 | | PK | 3-0 | 32-09-12 | D03700 | | | | 12 | | | TB0082Z | 7 | BJ | | ALL |
| 057 | 24 | | PK | 7-0 | 32-09-12 | D03700 | | | | 6 | | | TB0084Z | 10 | BJ | | ALL |
| 058 | 24 | | PK | 3-0 | 36-11-62 | D04346J | | | | 18 | | | D05768J | 19 | | | ALL |
| 059 | 24 | | PK | 3-0 | 36-11-62 | D04346J | | | | 19 | | | D05768J | 20 | | | ALL |
| 05A | 20 | | PA | 2-0 | 21-61-21 | D10150 | | | | 6 | | | GDX0002 | D.. | 2 | | ALL |
| 05B | 24 | | PK | 6-0 | 21-61-21 | D03716 | | | | X2 | | | TB0210Z | 12 | BJ | | ALL |
| 05C | 20 | | PA | 2-0 | 21-61-31 | D10154 | | | | 6 | | | GDX0002 | D.. | 2 | | ALL |
| 05D | 20 | | PA | 2-0 | 21-61-31 | D10154 | | | | 2 | | | GDX0002 | D.. | 2 | | ALL |
| 05E | 24 | | PK | 2-0 | 21-61-31 | D10154 | | | | 1 | | | D10156 | | 2 | | ALL |
| 05F | 22 | | PA | 6-0 | 21-61-31 | D10154 | | | | 4 | | | TB0212Z | 15 | BJ | | ALL |
| 05G | 24 | | PK | 3-0 | 21-61-31 | D10154 | | | | 7 | | | TB0254Z | 7 | BJ | | ALL |
| 05H | 22 | | PA | 6-0 | 21-61-31 | D10156 | | | | 1 | | | TB0212Z | 15 | BJ | | ALL |
| 05J | 24 | | PK | 3-0 | 21-61-31 | D10156 | | | | 5 | | | TB0254Y | A005 | BJ | | ALL |
| 05K | 24 | | PK | 2-0 | 21-61-31 | TB0088D | | | C002 | 2 | | | TB0254Z | 7 | BJ | | ALL |
| 05L | 20 | | PA | 2-0 | 21-61-31 | D10156 | | | | 6 | | | GDX0002 | D.. | 2 | | ALL |
| 05N | 24 | | PK | 6-0 | 21-61-31 | D05374J | | | | 6 | | | TB0212Z | 15 | BJ | | ALL |
| 05P | 24 | | PK | 6-0 | 21-61-31 | D03754 | | | | X2 | | | TB0212Z | 15 | BJ | | ALL |
| 05S | 20 | | PA | 2-0 | 36-11-62 | D10158 | | | | A1 | | | GDX0013 | D.. | 2 | | ALL |
| 05V | 22 | | PA | 7-0 | 74-31-21 | D10158 | | | | D1 | | * | TB0192X | A010 | BJ | | 050-099 |
| 05V | 22 | | PA | 7-0 | 74-31-21 | TB0192X | | | A010 | BJ | | | D10158 | D1 | | * | 150-199, 275-299 |
| 05W | 22 | | PA | 7-0 | 74-31-21 | D05328J | | | | 2 | | | D10158 | D2 | | | ALL |
| 05X | 22 | | PQ | CY | 7-0 | 74-31-21 | D10158 | | | B1 | | * | TB0192X | B010 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 5

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 05X | 22 | | PQ | CY | 12-0 | 74-31-21 | TB0192X | B010 | BJ | | D10158 | B1 | | * | 150-199, 275-299 |
| 05XZ | | | | CY | 0-0 | 74-31-21 | D10158 | DED | | | TB0192X | DED | | | 050-099 |
| 05XZ | | | | CY | 0-0 | 74-31-21 | TB0192X | DED | | | D10158 | DED | | | 150-199, 275-299 |
| 05Y | 22 | | PQ | CZ | 7-0 | 74-31-21 | D05326J | | 4 | | D10158 | B2 | | | ALL |
| 05YZ | | | | CZ | 0-0 | 74-31-21 | D05326J | DED | | | D10158 | DED | | | ALL |
| 060 | 24 | | PK | | 3-0 | 36-11-62 | D04346J | | 20 | | D05768J | 21 | | | ALL |
| 061 | 24 | | PK | | 6-0 | 36-11-62 | D04346J | | 22 | | TB0274G | 42 | 2 | | 050-099 |
| 061 | 24 | | PK | | 6-0 | 36-11-62 | D04346J | | 22 | | TB0212Y | C012 | BJ | | 150-154 |
| 061 | 24 | | PK | | 5-0 | 36-11-62 | D04346J | | 22 | | TB0274G | 42 | 2 | | 155-156, 162-166, 276 |
| 061 | 24 | | PK | | 10-0 | 36-11-62 | D04346J | | 22 | | TB0314Y | A005 | BJ | | 157, 167-199, 277-299 |
| 061 | 24 | | PK | | 3-0 | 36-11-62 | D04346J | | 22 | | TB0212Y | C012 | BJ | | 275 |
| 062 | 12 | | PA | | 6-0 | 24-51-24 | D06260J | | 6 | | TB5078 | 11 | C | | ALL |
| 065 | 12 | | PA | | 6-0 | 21-58-15 | D06288J | | 1 | | K00345 | A2 | E | | ALL |
| 066 | 12 | | PA | | 6-0 | 21-58-15 | D06288J | | 2 | | K00345 | B2 | E | | ALL |
| 067 | 12 | | PA | | 6-0 | 21-58-15 | D06288J | | 3 | | K00345 | C2 | E | | ALL |
| 06B | 22 | | PA | | 4-0 | 28-42-11 | D04346J | | 33 | | TB0304Y | A014 | BJ | | ALL |
| 06C | 24 | | PK | | 3-0 | 28-42-11 | D05374J | | 11 | | TB0304Y | A014 | BJ | | ALL |
| 06D | 22 | | PA | | 7-0 | 73-21-19 | D03752 | | X2 | | D03692 | 11 | | | 050-099, 150-199 |
| 06D | 22 | | PA | | 6-0 | 73-21-19 | D03752 | | X2 | | D03692 | 11 | | | 275-299 |
| 06E | 22 | | PA | | 5-0 | 73-21-19 | TB0274Y | A029 | BJ | | D03692 | 9 | | | 050-099 |
| 06E | 22 | | PA | | 7-0 | 73-21-19 | D03692 | | 9 | | TB0274Y | A029 | BJ | | 150-199 |
| 06E | 22 | | PA | | 9-0 | 73-21-19 | D03692 | | 9 | | TB0274Y | A029 | BJ | | 275-299 |
| 06F | 20 | | PA | | 12-0 | 30-21-11 | GDX0013 | | D.. | 2 | D12124 | 12 | | | 050-099 |
| 06F | 20 | | PA | | 10-0 | 30-21-11 | D12124 | | 12 | | GDX0013 | D.. | 2 | | 150-199 |
| 06F | 20 | | PA | | 3-0 | 73-21-19 | GDX0013 | | D.. | 2 | D10552 | 12 | | | 275-299 |
| 06G | 22 | | PA | | 12-0 | 30-21-11 | TB0254Z | | 8 | BJ | D12124 | 6 | | | 050-099 |
| 06G | 22 | | PA | | 12-0 | 30-21-11 | D12124 | | 6 | | TB0254Z | 8 | BJ | | 150-199 |
| 06G | 22 | | PA | | 10-0 | 73-21-19 | TB0274D | | C036 | 2 | D10552 | 6 | | | 275-299 |
| 06H | 22 | | PA | | 7-0 | 73-21-19 | TB0274Y | | A029 | BJ | D03730 | A1 | | | 050-099, 150-199 |
| 06H | 22 | | PA | | 6-0 | 73-21-19 | TB0274Y | | A029 | BJ | D03730 | A1 | | | 275-299 |
| 06J | 22 | | PA | | 12-0 | 73-21-19 | D05316J | | 41 | | D12124 | 14 | | | 050-099, 150-199 |
| 06J | 22 | | PA | | 8-0 | 73-21-19 | D05316J | | 41 | | D10552 | 13 | | | 275-299 |
| 06K | 24 | | PK | | 3-0 | 78-36-21 | D10088 | | 4 | | TB0254Y | A003 | BJ | | ALL |
| 06L | 24 | | PK | | 2-0 | 78-36-21 | D10088 | | 2 | | D10090 | 4 | | | ALL |
| 06M | 24 | | PK | | 8-0 | 78-36-21 | D05068J | | 44 | | TB0254Y | A003 | BJ | | 050-099, 150-156, 162-166, 275-276 |
| 06M | 24 | | PK | | 10-0 | 78-36-21 | D05068J | | 44 | | TB0254Y | A003 | BJ | | 157, 167-199, 277-299 |
| 06P | 24 | | PK | | 7-0 | 78-36-21 | D05068J | | 45 | | D05326J | 31 | | | ALL |
| 06Q | 24 | | PK | | 2-0 | 78-36-21 | D10088 | | 6 | | D10090 | 1 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 6

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 06R | 24 | | PK | 7-0 | 78-36-21 | D10088 | | 7 | | | | | TB0274Y | A003 | BJ | | ALL |
| 06S | 20 | | PA | 2-0 | 78-36-21 | D10088 | | 3 | | | | | GDX0001 | D.. | 2 | | ALL |
| 06T | 22 | | PA | 7-0 | 78-36-21 | TB0274D | | | C015 | 2 | | | D05068J | 50 | | | 050-099, 150-156, 162-166, 275-276 |
| 06T | 22 | | PA | 10-0 | 78-36-21 | TB0274D | | | C015 | 2 | | | D05068J | 50 | | | 157, 167-199, 277-299 |
| 06U | 22 | | PA | 2-0 | 78-36-21 | TB0274D | | | A015 | 2 | | | TB0274Y | A011 | BJ | | ALL |
| 06V | 24 | | PK | 7-0 | 78-36-21 | D10090 | | | | 2 | | | D20100 | B3 | | | 050-099, 150-156, 162-166, 275-276 |
| 06V | 24 | | PK | 10-0 | 78-36-21 | D10090 | | | | 2 | | | D20100 | B3 | | | 157, 167-199, 277-299 |
| 06W | 24 | | PK | 9-0 | 78-36-21 | D03690 | | | CAP | Y | | | D05326J | 49 | | | 050-099, 150-156, 162-166, 275-276 |
| 06W | 24 | | PK | 9-0 | SPARE | D03690 | | | CAP | Y | | | D05326J | 49 | | | 157, 167-199, 277-299 |
| 06X | 24 | | PK | 12-0 | 78-36-21 | D10090 | | | | 7 | | | TB0084Z | 14 | BJ | | ALL |
| 06Y | 20 | | PA | 2-0 | 78-36-21 | D10090 | | | | 3 | | | GDX0001 | D.. | 2 | | ALL |
| 070 | 18 | | PA | 3-0 | 33-31-11 | D05290J | | | | 11 | DK | | D05592J | 13 | | | ALL |
| 071 | 20 | | PA | 2-0 | 28-22-11 | K00189 | | | | X2 | C | | GDX0006 | D.. | 2 | | ALL |
| 072 | 24 | | PK | 10-0 | 28-22-11 | K00189 | | | | X1 | C | | D04284J | 1 | | | ALL |
| 077 | 24 | | PK | 8-0 | 21-61-51 | D05768J | | | | 1 | | | TB0254Z | 7 | BJ | | ALL |
| 078 | 24 | | PK | 6-0 | 31-31-22 | D05435J | | | | 32 | | | TB0192X | C004 | BJ | | 050-099 |
| 078 | 24 | | PK | 6-0 | 31-31-22 | TB0192X | | | C004 | BJ | | | D05435J | 32 | | | 150-199, 275-299 |
| 079 | 24 | | PK | 4-0 | 21-53-12 | D05352J | | | | 4 | | | D04646J | 2 | | | ALL |
| 07A | 20 | | PQ | HM | 6-0 | 78-34-21 | D03728 | | | C2 | | | TB0084Z | 14 | BJ | | 050-099, 150-156, 162-166, 275-276 |
| 07A | 20 | | PQ | HM | 8-0 | 78-34-21 | D03728 | | | C2 | | | TB0084Z | 14 | BJ | | 157, 167-199, 277-299 |
| 07AZ | | | | HM | 0-0 | 78-34-21 | D03728 | | | DED | | | TB0084Z | | | HM | ALL |
| 07B | 20 | | PA | | 3-0 | 73-21-19 | D03730 | | | A3 | | | GDX0015 | D.. | 2 | | ALL |
| 07C | 22 | | PA | | 8-0 | 73-21-19 | D12124 | | | 7 | | | D20544 | 13 | | | 050-099 |
| 07C | 22 | | PA | | 12-0 | 73-21-19 | D20544 | | | 13 | | | D12124 | 7 | | | 150-199 |
| 07C | 22 | | PA | | 8-0 | 73-21-19 | TB0274Y | | | A029 | % | | D10552 | 1 | | | 275-299 |
| 07K | 22 | | PA | | 4-0 | 79-33-11 | D05326J | | | 35 | | | TB0304Y | C017 | BJ | | ALL |
| 07L | 22 | | PA | | 4-0 | 79-33-11 | D05326J | | | 36 | | | TB0304Y | C017 | BJ | | ALL |
| 07M | 24 | | PK | | 3-0 | 79-33-11 | D05374J | | | 51 | | | TB0304Y | C017 | BJ | | ALL |
| 07Q | 22 | | PA | | 4-0 | 79-35-11 | D05326J | | | 37 | | | D05374J | 19 | | | ALL |
| 07R | 24 | | PK | | 9-0 | 24-51-52 | D03712 | | | C1 | | | D06260J | 18 | | | ALL |
| 07S | 24 | | PK | | 9-0 | 24-51-52 | D03712 | | | C2 | | | D06260J | 17 | | | ALL |
| 07T | 24 | | PK | | 7-0 | 29-11-12 | D05374J | | | 15 | | | TB0192Z | 17 | BJ | | ALL |
| 07U | 24 | | PK | | 7-0 | 29-11-12 | D05374J | | | 16 | | | TB0212Y | C010 | BJ | | ALL |
| 07Z | 22 | | PA | | 4-0 | 29-32-11 | D05068J | | | 22 | | | TB0304Y | C015 | BJ | | ALL |
| 080 | 24 | | PK | | 4-0 | 21-53-12 | D05352J | | | 5 | | | D04646J | 14 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 7

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 081 | 24 | | PK | | 4-0 | 21-53-12 | D05352J | | 6 | | D04646J | 24 | | | ALL |
| 082 | 24 | | PK | | 4-0 | 21-53-12 | D05352J | | 7 | | D04646J | 35 | | | ALL |
| 083 | 24 | | PK | | 4-0 | 21-53-12 | D05352J | | 8 | | D04646J | 36 | | | ALL |
| 084 | 24 | | PK | | 4-0 | 21-53-12 | D05352J | | 9 | | D04646J | 37 | | | ALL |
| 085 | 24 | | PK | | 4-0 | 21-53-12 | D05352J | | 10 | | D04646J | 38 | | | ALL |
| 087 | 16 | | PA | | 7-0 | 23-34-11 | D05541J | | 15 | | TB0190F | A002 | 2 | | 050-099, 275-299 |
| 087 | 16 | | PA | | 7-0 | 23-34-11 | D05541J | | 5 | FM | TB0190F | A002 | 2 | | 150-199 |
| 088 | 16 | | PA | | 7-0 | 23-34-11 | D05541J | | 19 | | TB0190F | C002 | 2 | | 050-099, 275-299 |
| 088 | 16 | | PA | | 7-0 | 23-34-11 | D05541J | | 6 | FM | TB0190F | C002 | 2 | | 150-199 |
| 08A | 24 | | PK | | 3-0 | 29-32-11 | D05374J | | 42 | | TB0304Y | C015 | BJ | | ALL |
| 08D | 22 | | PA | | 4-0 | 29-33-11 | D04346J | | 40 | | TB0304Y | A016 | BJ | | ALL |
| 08E | 24 | | PK | | 3-0 | 29-33-11 | D05374J | | 39 | | TB0304Y | A016 | BJ | | ALL |
| 08F | 24 | | PK | | 4-0 | 29-33-11 | D05374J | | 10 | | D04346J | 45 | | | ALL |
| 08H | 22 | | PA | | 3-0 | 27-23-11 | D05374J | | 14 | | TB0304Y | A015 | BJ | | ALL |
| 08J | 22 | | PA | | 4-0 | 27-23-11 | D05318J | | 3 | | TB0304Y | A015 | BJ | | ALL |
| 08K | 22 | | PA | | 6-0 | 27-81-11 | TB0210Y | | C001 | BJ | D05316J | 48 | | | ALL |
| 08L | 24 | | PK | | 9-0 | 32-61-14 | D04962J | | 23 | | TB0084Z | 10 | BJ | | ALL |
| 08M | 22 | | PA | | 3-0 | 30-21-11 | D10158 | | X1 | | TB0254Z | 8 | BJ | | ALL |
| 08N | 22 | | PA | | 10-0 | 30-21-11 | D10158 | | C2 | | D11828 | A3 | | | 050-099, 150-199 |
| 08N | 22 | | PA | | 3-0 | 30-21-11 | D10158 | | C2 | | TB0254Z | 8 | BJ | | 275-299 |
| 08P | 20 | | PA | | 2-0 | 30-21-11 | D10158 | | X2 | | GDX0002 | D.. | 2 | | ALL |
| 08Q | 22 | | PA | | 11-0 | 30-21-11 | TB0320Z | | 22 | BJ | D11828 | A2 | | | 050-099 |
| 08Q | 22 | | PA | | 12-0 | 30-21-11 | TB0320Z | | 22 | BJ | D11828 | A2 | | | 150-199 |
| 08Q | 22 | | PA | | 10-0 | 30-21-11 | D10158 | | C1 | | D11828 | A2 | | | 275-299 |
| 08S | 20 | | PA | | 6-0 | 30-71-24 | D05352J | | 20 | | TB0210Z | 11 | BJ | | 050-099, 150-199 |
| 08T | 16 | | PA | | 6-0 | 30-71-24 | D05352J | | 40 | | TB0210G | 6 | 2 | | 050-099, 150-199 |
| 08U | 24 | | PK | | 3-0 | 73-21-14 | D05326J | | 50 | | D04004J | 3 | | | 050-099, 150-199 |
| 08U | 24 | | PK | | 4-0 | 73-21-14 | D05326J | | 50 | | D04004J | 3 | | | 275-299 |
| 08V | 24 | | PK | | 8-0 | 21-61-21 | D10148 | | 3 | | TB0320Y | C033 | BJ | | 050-099 |
| 08V | 24 | | PK | | 9-0 | 21-61-21 | D10148 | | 3 | | TB0210Y | A001 | BJ | | 150-199, 275-278 |
| 08V | 24 | | PK | | 9-0 | 21-61-21 | D10148 | | 3 | | TB0320Y | C033 | BJ | | 280-299 |
| 08W | 24 | | PK | | 10-0 | 21-61-21 | TB0254Z | | 7 | BJ | TB0320Y | A033 | BJ | | 050-099 |
| 08W | 24 | | PK | | 8-0 | 21-61-21 | TB0320Y | | A033 | BJ | TB0254Z | 7 | BJ | | 150-199, 275-299 |
| 08X | 16 | | PA | | 6-0 | 38-13-11 | TB0210G | | 8 | 2 | D05660J | 11 | | | 150-199 |
| 08Y | 24 | | PK | | 9-0 | 24-51-71 | D06260J | | 21 | | D03728 | B2 | | | ALL |
| 08Z | 24 | | PK | | 9-0 | 24-51-71 | D06260J | | 22 | | D03728 | B1 | | | ALL |
| 091 | 24 | | PK | | 3-0 | 36-11-62 | D04346J | | 47 | | D05768J | 24 | | | ALL |
| 092 | 24 | | PK | | 3-0 | 36-11-62 | D04346J | | 48 | | D05768J | 2 | | | ALL |
| 093 | 22 | | PA | | 3-0 | 36-22-11 | D05768J | | 34 | | D04346J | 6 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 8

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 094 | 24 | | PK | 8-0 | 29-11-12 | D04962J | | 4 | | | | | D00618 | A3 | | | ALL |
| 095 | 24 | | PK | 5-0 | 31-31-22 | D05499J | | 20 | | | | | TB0304X | B009 | BJ | | 050-099 |
| 095 | 24 | | PK | 5-0 | 31-31-22 | TB0304X | | | C007 | BJ | | | D05499J | 20 | | | 150-199, 275-299 |
| 096 | 24 | | PK | 5-0 | 31-31-22 | D05499J | | 19 | | | | | TB0304X | C009 | BJ | | 050-099 |
| 096 | 24 | | PK | 5-0 | 31-31-22 | TB0304X | | | D007 | BJ | | | D05499J | 19 | | | 150-199, 275-299 |
| 097 | 20 | | PA | 4-0 | 33-44-11 | D04962J | | 3 | | | | | TB0304Y | C016 | BJ | | ALL |
| 098 | 24 | | PK | 6-0 | 31-31-12 | D05435J | | 30 | | | | | D01644 | 3 | | | ALL |
| 099 | 24 | | PK | 6-0 | 31-31-12 | D05435J | | 31 | | | | | D01644 | 7 | | | ALL |
| 09A | 24 | | PK | 4-0 | 21-51-21 | D05352J | | 28 | | | | | TB0304Y | A012 | BJ | | ALL |
| 09B | 24 | | PK | 5-0 | 21-53-21 | D05352J | | 32 | | | | | TB0304X | C002 | BJ | | ALL |
| 09C | 24 | | PK | 5-0 | 21-53-21 | D05352J | | 33 | | | | | TB0304X | D002 | BJ | | ALL |
| 09D | 24 | | PK | 5-0 | 21-53-21 | D05352J | | 34 | | | | | TB0304X | A003 | BJ | | ALL |
| 09E | 24 | | PK | 5-0 | 21-53-21 | D05352J | | 35 | | | | | TB0304X | B003 | BJ | | ALL |
| 09F | 24 | | PK | 5-0 | 21-53-21 | D05352J | | 36 | | | | | TB0304X | C003 | BJ | | ALL |
| 09G | 24 | | PK | 5-0 | 21-53-21 | D05352J | | 37 | | | | | TB0304X | D003 | BJ | | ALL |
| 09J | 24 | | PK | 8-0 | 32-09-12 | D03690 | | 12 | | | | | TB0082Z | 7 | BJ | | ALL |
| 09K | 24 | | PK | 3-0 | 32-09-12 | D03690 | | 6 | | | | | TB0084Z | 9 | BJ | | ALL |
| 09L | 22 | | PA | 3-0 | 29-11-12 | D04962J | | 30 | | | | | D05612J | 3 | | | ALL |
| 09M | 22 | | PA | 3-0 | 28-22-21 | D05316J | | 58 | | | | | D05374J | 46 | | | ALL |
| 09Q | 24 | | PK | 3-0 | 73-21-18 | D05374J | | 54 | | | | | D05316J | 30 | | | ALL |
| 09T | 24 | | PK | 10-0 | 29-11-12 | M00499 | | A | | C | | | TB0084Y | A002 | BJ | | ALL |
| 09U | 24 | | PV | HG | 8-0 | 80-11-21 | D05612J | | 25 | | | | D10394 | X1 | | | 050-099 |
| 09U | 24 | | PV | HG | 9-0 | 80-11-21 | D10394 | | X1 | | | | D05612J | 25 | | | 150-199, 275-299 |
| 09UZ | | | | HG | 0-0 | 80-11-21 | D05612J | | DED | | | | D10394 | DED | | | 050-099 |
| 09UZ | | | | HG | 0-0 | 80-11-21 | D10394 | | DED | | | | D05612J | DED | | | 150-199, 275-299 |
| 09W | 24 | | PV | CJ | 8-0 | 29-11-31 | D05612J | | 35 | | | | D10394 | B3 | | | ALL |
| 09WZ | | | | CJ | 0-0 | 29-11-31 | D05612J | | DED | | | | D10394 | DED | | | ALL |
| 09X | 24 | | PV | CK | 8-0 | 29-11-31 | D05612J | | 36 | | | | D10392 | B2 | | | ALL |
| 09XZ | | | | CK | 0-0 | 29-11-31 | D05612J | | DED | | | | D10392 | DED | | | ALL |
| 0AA | 22 | | PA | | 9-0 | 36-11-52 | D10528 | | 4 | | | | GDX0017 | D.. | 2 | | ALL |
| 0AB | 24 | | PK | | 8-0 | 36-11-52 | D10528 | | 5 | | | | D04004J | 10 | | | ALL |
| 0AE | 22 | | PA | | 8-0 | 36-11-62 | D05068J | | 24 | | | | TB0190Y | A011 | BJ | | 050-099, 150-155, 162-165, 275-276 |
| 0AE | 22 | | PA | | 5-0 | 36-11-62 | D05068J | | 24 | | | | TB0320Y | A019 | BJ | | 156-157, 166-199, 277-299 |
| 0AF | 22 | | PA | | 8-0 | 36-11-62 | D05768J | | 17 | | | | TB0190Y | A011 | BJ | | 050-099, 150-155, 162-165, 275-276 |
| 0AF | 22 | | PA | | 5-0 | 36-11-62 | D05768J | | 17 | | | | TB0320Y | A019 | BJ | | 156-157, 166-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 9

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 0AG | 22 | | PA | | 8-0 | 36-11-62 | D05768J | | 56 | | TB0190Y | C011 | BJ | | 050-099, 150-155, 162-165, 275-276 |
| 0AG | 22 | | PA | | 5-0 | 36-11-62 | D05768J | | 56 | | TB0320Y | C019 | BJ | | 156, 166 |
| 0AG | 22 | | PA | | 5-0 | 36-11-62 | D05768J | | 7 | | TB0320Y | C019 | BJ | | 157, 167-199, 277-299 |
| 0AH | 22 | | PA | | 8-0 | 36-11-62 | D05068J | | 25 | | TB0190Y | C011 | BJ | | 050-099, 150-155, 162-165, 275-276 |
| 0AH | 22 | | PA | | 5-0 | 36-11-62 | D05068J | | 25 | | TB0320Y | C019 | BJ | | 156-157, 166-199, 277-299 |
| 0AI | 22 | | PA | | 5-0 | 36-11-62 | D05068J | | 16 | | TB0320Y | A009 | BJ | | 157, 167-199, 277-299 |
| 0AJ | 22 | | PA | | 8-0 | 36-11-62 | D05768J | | 50 | | TB0086D | C006 | 2 | | 050-099, 150-155, 163-165, 275-276 |
| 0AJ | 22 | | PA | | 10-0 | 36-11-62 | D05768J | | 50 | | TB0086D | C006 | 2 | | 156, 162, 166 |
| 0AJ | 22 | | PA | | 5-0 | 36-11-62 | D05768J | | 50 | | TB0320Y | A009 | BJ | | 157, 167-199, 277-299 |
| 0AK | 24 | | PK | | 8-0 | 36-21-11 | D04004J | | 7 | | TB0190Y | C005 | BJ | | 050-099, 150-155, 163-165, 275-276 |
| 0AK | 24 | | PK | | 5-0 | 36-21-11 | D04004J | | 7 | | TB0320Y | C009 | BJ | | 156-157, 166-199, 277-299 |
| 0AK | 24 | | PK | | 8-0 | 36-21-11 | D04004J | | 7 | | TB0320Y | C009 | BJ | | 162 |
| 0AL | 24 | | PK | | 8-0 | 36-21-11 | D04346J | | 49 | | TB0190Y | C005 | BJ | | 050-099, 150-155, 163-165, 275-276 |
| 0AL | 24 | | PK | | 5-0 | 36-21-11 | D04346J | | 49 | | TB0320Y | C009 | BJ | | 156-157, 166-199, 277-299 |
| 0AL | 24 | | PK | | 8-0 | 36-21-11 | D04346J | | 49 | | TB0320Y | C009 | BJ | | 162 |
| 0AR | 24 | | PK | | 4-0 | 36-23-21 | D05068J | | 12 | | D04004J | | 25 | | 050-099, 150-157, 163-199, 275-299 |
| 0AR | 24 | | PK | | 6-0 | 36-23-21 | D05068J | | 12 | | D04004J | | 25 | | 162 |
| 0AT | 24 | | PK | | 4-0 | 36-23-21 | D05068J | | 26 | | D04004J | | 27 | | 050-099, 150-157, 163-199, 275-299 |
| 0AT | 24 | | PK | | 6-0 | 36-23-21 | D05068J | | 26 | | D04004J | | 27 | | 162 |
| 0AU | 24 | | PK | | 4-0 | 36-23-21 | D05068J | | 15 | | D04004J | | 28 | | 050-099, 150-157, 163-199, 275-299 |
| 0AU | 24 | | PK | | 6-0 | 36-23-21 | D05068J | | 15 | | D04004J | | 28 | | 162 |
| 102 | 24 | | PK | | 6-0 | 31-31-11 | TB0210Y | | C016 | BJ | D03714 | | A2 | | ALL |
| 103 | 24 | | PK | | 6-0 | 31-31-11 | TB0210Y | | A016 | BJ | D03714 | | A3 | | ALL |
| 105 | 22 | | PA | | 10-0 | 29-11-12 | M00925 | | A | C | TB0082Y | A005 | BJ | | ALL |
| 106 | 22 | | PA | | 9-0 | 34-12-21 | D05435J | | 13 | | T00140 | | HV | D | ALL |
| 107 | 22 | | PA | | 9-0 | 34-12-21 | D05435J | | 14 | | T00140 | | LV | D | ALL |
| 108 | 22 | | PA | | 9-0 | 34-12-21 | D05435J | | 15 | | T00140 | | GND | D | ALL |
| 109 | 24 | | PK | | 7-0 | 29-11-12 | TB0274D | | A026 | 2 | M00302 | | B | C | ALL |

WIRE LIST
D280T132

91-21-11
Section W0190
Page 10
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | |
| 10J | 24 | | PK | | 7-0 | 21-61-51 | D04962J | | | | 24 | | | | ALL | |
| 10L | 24 | | PK | | 3-0 | 34-12-22 | D05437J | | | | 16 | | | | ALL | |
| 10M | 24 | | PK | | 6-0 | 29-11-12 | D04962J | | | | 17 | | | C026 | 2 | ALL |
| 10N | 22 | | PA | | 6-0 | 29-11-12 | D04962J | | | | 16 | | | C025 | 2 | ALL |
| 110 | 24 | | PK | | 10-0 | 32-09-12 | D05316J | | | | 56 | | | B | C | ALL |
| 111 | 24 | | PK | | 8-0 | 36-11-21 | D04004J | | | | 13 | | | X2 | | ALL |
| 112 | 24 | | PK | | 8-0 | 36-11-21 | D04004J | | | | 14 | | | X2 | | ALL |
| 113 | 20 | | PQ | CT | 3-0 | 27-32-31 | D05266J | | | | 22 | | | 48 | | ALL |
| 113Z | | | | CT | 0-0 | 27-32-31 | D05266J | | | | DED | | | DED | | ALL |
| 115 | 16 | | PQ | D | 3-0 | 21-58-11 | D06260J | | | | 8 | FM | | 22 | FM | 050-099 |
| 115 | 16 | | PQ | D | 3-0 | 21-58-11 | D06260J | | | | 8 | | | 22 | FM | 150-199, 275-299 |
| 115Z | | | | D | 0-0 | 21-58-11 | D06260J | | | | DED | | | DED | | ALL |
| 116 | 24 | | PK | | 3-0 | 36-11-21 | D04004J | | | | 11 | | | 42 | | ALL |
| 119 | 24 | | PK | | 7-0 | 34-12-22 | D05435J | | | | 17 | | | 2 | | ALL |
| 11A | 20 | | PA | | 3-0 | 80-11-11 | D10392 | | | | X2 | | | D.. | 2 | ALL |
| 11C | 24 | | PV | HH | 8-0 | 80-11-11 | D10392 | | | | X1 | | | 10 | | ALL |
| 11CZ | | | | HH | 0-0 | 80-11-11 | D10392 | | | | DED | | | DED | | ALL |
| 11D | 24 | | PK | | 3-0 | 29-11-12 | D10392 | | | | A3 | | | A2 | | ALL |
| 11F | 20 | | PA | | 3-0 | 80-11-21 | D10394 | | | | X2 | | | D.. | 2 | ALL |
| 11H | 24 | | PK | | 3-0 | 29-11-12 | D03728 | | | | D3 | | | A002 | BJ | ALL |
| 11J | 24 | | PK | | 3-0 | 29-11-12 | D10394 | | | | A3 | | | A002 | BJ | ALL |
| 11K | 24 | | PK | | 3-0 | 29-11-12 | D03728 | | | | D1 | | | A2 | | ALL |
| 11M | 22 | | PQ | DB | 6-0 | 29-11-12 | D04004J | | | | 29 | | | C012 | 2 | ALL |
| 11MZ | | | | DB | 0-0 | 29-11-12 | D04004J | | | | DED | | | DED | | ALL |
| 11N | 24 | | PV | CL | 2-0 | 29-11-31 | D10392 | | | | B3 | | | B2 | | ALL |
| 11NZ | | | | CL | 0-0 | 29-11-31 | D10392 | | | | DED | | | DED | | ALL |
| 120 | 24 | | PK | | 8-0 | 23-12-21 | D00640 | | | | 7 | | | 11 | | 050-099 |
| 120 | 24 | | PK | | 9-0 | 23-12-21 | D05541J | | | | 11 | | | 7 | | 150-199, 275-299 |
| 121 | 22 | | PA | | 5-0 | 49-61-11 | D00640 | | | | 2 | | | 18 | BJ | ALL |
| 122 | 22 | | PA | | 6-0 | 31-31-11 | D05435J | | | | 25 | | | C016 | BJ | ALL |
| 123 | 22 | | PA | | 6-0 | 49-61-11 | D00640 | | | | 1 | | | C022 | 2 | ALL |
| 124 | 20 | | PQ | YE | 5-0 | 73-21-19 | D03752 | | | | A1 | | | 52 | | 050-099 |
| 124 | 20 | | PQ | BC | 6-0 | 73-21-19 | D05316J | | | | 52 | | | A1 | | 150-199 |
| 124 | 20 | | PQ | BC | 5-0 | 73-21-19 | D05316J | | | | 52 | | | A1 | | 275-299 |
| 124Z | | | | YE | 0-0 | 73-21-19 | D03752 | | | | | | | 6 | | 050-099 |
| 124Z | | | | BC | 0-0 | 73-21-19 | D05316J | | | | 6 | | | | | 150-199, 275-299 |
| 125 | 24 | | PV | BP | 7-0 | 29-11-12 | TB0190D | | | | A012 | 2 | | B | C | ALL |
| 125Z | | | | BP | 0-0 | 29-11-12 | TB0190D | | | | DED | | | DED | | ALL |
| 126 | 22 | | PQ | BN | 2-0 | 29-11-12 | TB0190D | | | | C012 | 2 | | C010 | BJ | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 11

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 126Z | | | | BN | 0-0 | 29-11-12 | TB0190D | | | | TB0212Y | DED | | | ALL |
| 127 | 20 | PA | | | 4-0 | 33-43-11 | D04340J | | | | D04346J | 9 | | | 050-099 |
| 127 | 18 | PA | | | 4-0 | 33-43-11 | D04340J | | DK | | D04346J | 9 | DK | | 150-199, 275-299 |
| 128 | 20 | PA | | | 4-0 | SPARE | D04340J | | | | D04346J | 11 | | | 050-099 |
| 128 | 18 | PA | | | 4-0 | SPARE | D04340J | | DK | | D04346J | 11 | DK | | 150-199, 275-299 |
| 129 | 20 | PA | | | 3-0 | 33-42-21 | D04340J | | | | D05068J | 21 | | | 050-099 |
| 129 | 18 | PA | | | 3-0 | 33-42-21 | D04340J | | DK | | D05068J | 36 | DK | | 150-155, 162-165, 275-276 |
| 129 | 18 | PA | | | 4-0 | 33-42-21 | D04340J | | DK | | D05068J | 36 | DK | | 156-157, 166-199, 277-299 |
| 12A | 24 | PK | | | 5-0 | 73-33-11 | D05326J | | | | D05374J | 48 | | | 050-099 |
| 12A | 24 | PK | | | 4-0 | 73-33-11 | D05374J | | | | D05326J | 51 | | | 150-199, 275-299 |
| 12B | 24 | PK | | | 5-0 | 73-33-11 | D05326J | | | | D05374J | 47 | | | 050-099 |
| 12B | 24 | PK | | | 4-0 | 73-33-11 | D05374J | | | | D05326J | 52 | | | 150-199, 275-299 |
| 12F | 24 | PK | | | 2-0 | 29-11-12 | TB0082Z | | BJ | | TB0082D | C012 | 2 | | ALL |
| 12G | 24 | PK | | | 8-0 | 29-11-12 | D03728 | | | | TB0082D | A012 | 2 | | ALL |
| 12H | 24 | PK | | | 8-0 | 29-11-12 | D05612J | | | | TB0082D | C012 | 2 | | ALL |
| 12R | 16 | PA | | | 9-0 | 28-22-11 | D05602J | | | | K00189 | A2 | D | | ALL |
| 12S | 16 | PA | | | 9-0 | 28-22-11 | D05602J | | | | K00189 | B2 | D | | ALL |
| 12T | 16 | PA | | | 9-0 | 28-22-11 | D05602J | | | | K00189 | C2 | D | | ALL |
| 12U | 12 | PA | | | 10-0 | 28-22-12 | D06260J | | | | K00330 | A2 | D | | ALL |
| 12V | 12 | PA | | | 10-0 | 28-22-12 | D06260J | | | | K00330 | B2 | D | | ALL |
| 12W | 12 | PA | | | 10-0 | 28-22-12 | D06260J | | | | K00330 | C2 | D | | ALL |
| 12X | 24 | PK | | | 5-0 | 27-51-61 | D10454 | | A3 | | TB0212Y | A010 | BJ | | ALL |
| 12Y | 24 | PK | | | 6-0 | 27-51-61 | D10454 | | X1 | | TB0192X | D005 | BJ | | ALL |
| 12Z | 24 | PK | | | 6-0 | 27-51-61 | D10454 | | X2 | | TB0192X | C008 | BJ | | ALL |
| 130 | 20 | PA | | | 9-0 | 21-45-11 | D04340J | | | | D03730 | B2 | | | ALL |
| 131 | 18 | PA | | | 3-0 | 38-32-11 | D05688J | | DK | | D04284J | 21 | | | 050-099, 150-199, 277-299 |
| 131 | 18 | PA | | | 5-0 | 38-32-11 | D04004J | | DK | | D05688J | 11 | DK | | 275-276 |
| 132 | 22 | PA | | | 3-0 | 29-11-31 | D05352J | | | | D05068J | 14 | | | ALL |
| 133 | 24 | PK | | | 10-0 | 36-11-21 | D05352J | | | | TB0084Y | C008 | BJ | | ALL |
| 134 | 22 | PA | | | 9-0 | 36-11-21 | D05352J | | | | D03666 | A2 | | | ALL |
| 135 | 22 | PA | | | 9-0 | 36-11-21 | D05352J | | | | D03668 | A2 | | | ALL |
| 136 | 18 | PA | | | 4-0 | 33-44-21 | TB0304G | | 2 | | D05068J | 1 | DK | | 050-099, 150-155, 162-165, 275-276 |
| 136 | 18 | PA | | | 5-0 | 33-44-21 | TB0304G | | 2 | | D05068J | 1 | DK | | 156-157, 166-199, 277-299 |
| 137 | 20 | PA | | | 5-0 | 33-44-11 | D04340J | | | | TB0304Y | C016 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 12

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 138 | 20 | | PA | 7-0 | 21-45-11 | D03730 | | B1 | | | | | TB0192X | B008 | BJ | | ALL |
| 139 | 18 | | PA | 3-0 | 33-31-11 | D05592J | | 9 | | | | | D05592J | 12 | | | ALL |
| 13A | 20 | | PA | 3-0 | 27-51-61 | D10454 | | A2 | | | | | GDX0002 | D.. | 2 | | ALL |
| 13B | 24 | | PK | 6-0 | 21-61-81 | D05602J | | 11 | | | | | TB0274Y | C029 | BJ | | ALL |
| 13C | 24 | | PK | 5-0 | 34-61-25 | D01725 | | X1 | | | | | D05499J | 1 | | | 050-099, 275-299 |
| 13C | 24 | | PK | 6-0 | 34-61-25 | D01725 | | X1 | | | | | D05499J | 1 | | | 150-199 |
| 13D | 20 | | PA | 6-0 | 34-61-25 | D01725 | | X2 | | | | | D05499J | 11 | | | 050-099, 150-199 |
| 13D | 20 | | PA | 8-0 | 34-61-25 | D01725 | | X2 | | | | | D05499J | 11 | | | 275-299 |
| 13E | 22 | | PA | 6-0 | 27-81-11 | D05316J | | 49 | | | | | TB0212Y | C009 | BJ | | ALL |
| 13F | 20 | | PA | 8-0 | 36-11-41 | D10582 | | 5 | | | | | GDX0005 | D.. | 2 | | 050-099 |
| 13F | 20 | | PA | 9-0 | 36-11-41 | D10582 | | 5 | | | | | GDX0005 | D.. | 2 | | 162-199 |
| 13F | 20 | | PA | 4-0 | 36-11-41 | D10582 | | 5 | | | | | GDX0006 | D.. | 2 | | 275-299 |
| 13I | 24 | | PK | 7-0 | 36-11-41 | D05352J | | 31 | | | | | TB0274D | C031 | 2 | | ALL |
| 13J | 24 | | PK | 5-0 | 36-11-41 | D05068J | | 6 | | | | | D01724 | A3 | | | ALL |
| 13K | 24 | | PK | 6-0 | 36-11-41 | D05068J | | 7 | | | | | TB0274Y | C033 | BJ | | ALL |
| 13L | 24 | | PK | 6-0 | 36-11-41 | D01724 | | A2 | | | | | TB0274Y | C033 | BJ | | ALL |
| 13M | 24 | | PK | 7-0 | 36-11-41 | D10528 | | 2 | | | | | TB0274Y | C033 | BJ | | ALL |
| 13N | 24 | | PK | 6-0 | 36-11-41 | D01726 | | A2 | | | | | TB0274F | A032 | 2 | | ALL |
| 13P | 24 | | PK | 6-0 | 36-11-41 | D01726 | | A3 | | | | | D05352J | 30 | | | ALL |
| 13Q | 24 | | PK | 5-0 | 36-11-41 | D01726 | | X2 | | | | | D05068J | 5 | | | ALL |
| 13R | 24 | | PK | 6-0 | 36-11-41 | D01726 | | X1 | | | | | TB0274Y | A033 | BJ | | ALL |
| 13S | 24 | | PK | 6-0 | 36-11-41 | D05068J | | 8 | | | | | TB0274Y | A034 | BJ | | ALL |
| 13T | 24 | | PK | 7-0 | 36-11-41 | D10528 | | 1 | | | | | TB0274Y | A034 | BJ | | ALL |
| 13U | 22 | | PA | 5-0 | 36-11-52 | D10528 | | 6 | | | | | SM00025 | 9 | | | 050-099, 155 |
| 13U | 22 | | PA | 6-0 | 36-11-52 | D10528 | | 6 | | | | | SM00025 | 9 | | | 150-154, 156, 162-166 |
| 13U | 22 | | PA | 5-0 | 36-11-52 | D10528 | | 6 | | | | | TB0254Y | C004 | BJ | | 157, 167-199, 277-299 |
| 13U | 22 | | PA | 7-0 | 36-11-52 | D10528 | | 6 | | | | | SM00025 | 9 | | | 275-276 |
| 13V | 22 | | PA | 7-0 | 36-11-52 | D10528 | | 12 | | | | | D05768J | 38 | | | ALL |
| 13X | 24 | | PK | 6-0 | 36-11-41 | D05688J | | 5 | | | | | TB0274Y | A033 | BJ | | ALL |
| 140 | 24 | | PK | 8-0 | 32-31-11 | D04646J | | 1 | | | | | D03712 | A1 | | | ALL |
| 141 | 24 | | PK | 8-0 | 32-42-12 | D04646J | | 7 | | | | | D03698 | 13 | | | ALL |
| 142 | 24 | | PK | 8-0 | 32-42-12 | D04646J | | 8 | | | | | D03698 | 1 | | | ALL |
| 143 | 24 | | PK | 3-0 | 32-41-11 | D04646J | | 3 | | | | | D04346J | 1 | | | ALL |
| 144 | 24 | | PK | 3-0 | 32-41-11 | D05328J | | 39 | | | | | D04346J | 2 | | | ALL |
| 145 | 24 | | PK | 3-0 | 32-41-11 | D05328J | | 40 | | | | | D04346J | 3 | | | ALL |
| 146 | 24 | | PK | 8-0 | 21-26-11 | D04646J | | 9 | | | | | D03788 | A3 | | | ALL |
| 148 | 24 | | PK | 6-0 | 21-58-16 | D04646J | | 11 | | | | | D10892 | A2 | | | ALL |
| 14D | 22 | | PA | 10-0 | 27-81-11 | D05374J | | 3 | | | | | TB0084Y | A001 | BJ | | ALL |
| 14E | 22 | | PA | 3-0 | 27-81-11 | D01926 | | B2 | | | | | TB0084Y | A001 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 13

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 14F | 20 | | PA | | 3-0 | 27-81-11 | D01926 | | B1 | | GDX0007 | D.. | 2 | | ALL |
| 14G | 24 | | PV | BX | 5-0 | 73-21-11 | D06076J | | 10 | | TB0304X | B007 | BJ | | 050-099 |
| 14G | 24 | | PV | DD | 5-0 | 73-21-11 | D06076J | | 10 | | TB0304X | B007 | BJ | | 150-199, 277-299 |
| 14G | 24 | | PV | DD | 5-0 | 73-21-11 | D06076J | | 10 | | TB0304X | C008 | BJ | | 275-276 |
| 14GZ | | | | BX | 0-0 | 73-21-11 | D06076J | | 16 | | TB0304X | B008 | BJ | | 050-099 |
| 14GZ | | | | DD | 0-0 | 73-21-11 | D06076J | | 16 | | TB0304X | B008 | BJ | | 150-199, 277-299 |
| 14GZ | | | | DD | 0-0 | 73-21-11 | D06076J | | 16 | | TB0304X | A009 | BJ | | 275-276 |
| 14H | 22 | | PA | | 3-0 | 27-81-21 | D02918 | | B2 | | TB0084Y | A001 | BJ | | ALL |
| 14M | 22 | | PA | | 6-0 | 31-31-11 | D05435J | | 7 | | TB0210X | D019 | BJ | | 050-099 |
| 14M | 22 | | PA | | 7-0 | 31-31-11 | TB0210X | | D019 | BJ | D05435J | 7 | | | 150-199, 275-299 |
| 14N | 20 | | PA | | 3-0 | 27-81-21 | D02918 | | B1 | | GDX0007 | D.. | 2 | | ALL |
| 14P | 20 | | PA | | 1-0 | 29-11-12 | M00499 | | G | C | GDX0018 | D.. | E | | 050-099 |
| 14P | 20 | | PA | | 0-12 | 29-11-12 | M00499 | | G | C | GDX0018 | D.. | E | | 150-199, 275-299 |
| 14Q | 18 | | PA | | 7-0 | 21-26-11 | D10724 | | X1 | | K00346 | A1 | E | | 050-099, 150-155, 162-165, 275-276 |
| 14Q | 24 | | PK | | 8-0 | 21-26-11 | D10724 | | X1 | | D04962J | 15 | | | 156-157, 166-199, 277-299 |
| 14R | 18 | | PA | | 3-0 | 21-26-11 | D10724 | | X2 | | GDX0006 | A.. | 2 | | 050-099, 275-276 |
| 14R | 18 | | PA | | 4-0 | 21-26-11 | D10724 | | X2 | | GDX0006 | A.. | 2 | | 150-155, 162-165 |
| 14R | 20 | | PA | | 6-0 | 21-26-11 | D10724 | | X2 | | GDX0017 | A.. | 2 | | 156-157, 166-199, 277-299 |
| 14T | 20 | | PA | | 3-0 | 21-26-11 | D10724 | | A2 | | GDX0006 | D.. | 2 | | 050-099, 275-276 |
| 14T | 20 | | PA | | 4-0 | 21-26-11 | D10724 | | A2 | | GDX0006 | D.. | 2 | | 150-155, 162-165 |
| 14T | 20 | | PA | | 5-0 | 21-26-11 | D10724 | | A2 | | GDX0017 | D.. | 2 | | 156-157, 166-199 |
| 14T | 20 | | PA | | 6-0 | 21-26-11 | D10724 | | A2 | | GDX0017 | D.. | 2 | | 277-299 |
| 14V | 24 | | PK | | 9-0 | 21-26-11 | D10724 | | B2 | | D04646J | 48 | | | ALL |
| 14Y | 24 | | PK | | 9-0 | 21-26-11 | D10724 | | B1 | | D04646J | 49 | | | ALL |
| 150 | 24 | | PK | | 6-0 | 21-25-21 | D04646J | | 18 | | TB0192Y | A013 | BJ | | ALL |
| 151 | 22 | | PA | | 5-0 | 21-25-21 | D04646J | | 19 | | TB0210Y | C015 | BJ | | ALL |
| 152 | 24 | | PK | | 6-0 | 21-25-21 | D04646J | | 20 | | TB0192Y | A013 | BJ | | ALL |
| 153 | 24 | | PK | | 4-0 | 21-25-21 | D04646J | | 21 | | K00416 | X2 | C | | ALL |
| 154 | 24 | | PK | | 5-0 | 21-25-21 | D04646J | | 23 | | TB0304X | A001 | BJ | | ALL |
| 155 | 24 | | PK | | 3-0 | 21-53-12 | D04646J | | 39 | | D04962J | 11 | | | ALL |
| 156 | 24 | | PK | | 9-0 | 78-34-21 | D05316J | | 8 | | D03670 | X2 | | | ALL |
| 157 | 24 | | PK | | 12-0 | 78-34-21 | D05316J | | 55 | | TB0084Z | 14 | BJ | | 050-099 |
| 157 | 22 | | PA | | 12-0 | 78-34-21 | D05316J | | 55 | | TB0084Z | 14 | BJ | | 150-199, 275-299 |
| 158 | 24 | | PK | | 3-0 | 21-53-12 | D04646J | | 40 | | D04962J | 12 | | | ALL |
| 159 | 24 | | PK | | 3-0 | 21-53-12 | D04646J | | 41 | | D04962J | 13 | | | ALL |
| 15A | 24 | | PK | | 9-0 | 32-09-12 | M01163 | | A | C | D02904 | 12 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 14

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 15B | 24 | | PK | 10-0 | 32-09-12 | M01164 | | A | C | | | | TB0082Z | 8 | BJ | | ALL |
| 15C | 24 | | PK | 9-0 | 21-61-41 | D10686 | | X1 | | | | | TB0254Z | 7 | BJ | | ALL |
| 15D | 24 | | PK | 11-0 | 21-61-41 | TB0254Z | | 7 | BJ | | | | TB0082D | C016 | 2 | | ALL |
| 15E | 24 | | PK | 3-0 | 21-61-41 | D10688 | | X1 | | | | | TB0082D | C016 | 2 | | ALL |
| 15F | 24 | | PK | 3-0 | 21-61-41 | D10688 | | X2 | | | | | TB0082D | A016 | 2 | | ALL |
| 15G | 24 | | PK | 1-0 | 21-61-41 | TB0082Y | | C005 | BJ | | | | TB0082D | A016 | 2 | | ALL |
| 15H | 24 | | PK | 3-0 | 21-61-41 | D10688 | | A1 | | | | | TB0082Y | C005 | BJ | | ALL |
| 15I | 22 | | PA | 3-0 | 21-61-41 | D10688 | | B1 | | | | | TB0082Z | 13 | BJ | | ALL |
| 15J | 20 | | PA | 3-0 | 21-61-41 | D10688 | | B2 | | | | | GD0004 | D.. | 2 | | ALL |
| 15K | 24 | | PK | 2-0 | 21-61-41 | D10686 | | B1 | | | | | D10688 | A2 | | | ALL |
| 15L | 20 | | PA | 3-0 | 21-61-41 | D10686 | | B2 | | | | | GD0004 | D.. | 2 | | ALL |
| 15M | 20 | | PA | 3-0 | 21-61-41 | D10686 | | A2 | | | | | GD0004 | D.. | 2 | | ALL |
| 15N | 22 | | PA | 3-0 | 21-61-41 | D10686 | | A3 | | | | | TB0082Z | 13 | BJ | | ALL |
| 15P | 22 | | PA | 9-0 | 21-61-41 | D05768J | | 35 | | | | | TB0082Z | 13 | BJ | | ALL |
| 15Q | 24 | | PK | 10-0 | 21-61-41 | D05374J | | 9 | | | | | TB0082Z | 13 | BJ | | ALL |
| 15R | 24 | | PK | 3-0 | 21-61-41 | D10690 | | X2 | | | | | TB0082Z | 13 | BJ | | ALL |
| 15S | 24 | | PK | 8-0 | 21-61-41 | D05768J | | 36 | | | | | D10690 | X1 | | | ALL |
| 15T | 24 | | PK | 9-0 | 21-61-41 | D05768J | | 37 | | | | | TB0082Y | A001 | BJ | | 050-099, 150-199 |
| 15T | 24 | | PK | 8-0 | 21-61-41 | TB0082Y | | A001 | BJ | | | | D05768J | 37 | | | 275-299 |
| 15U | 24 | | PK | 9-0 | 21-61-41 | D05768J | | 41 | | | | | TB0082Y | C005 | BJ | | ALL |
| 15V | 24 | | PK | 8-0 | 21-61-41 | D05768J | | 43 | | | | | D10690 | C2 | | | ALL |
| 15W | 24 | | PK | 8-0 | 21-61-41 | D05768J | | 44 | | | | | D10690 | D3 | | | ALL |
| 15X | 24 | | PK | 8-0 | 21-61-41 | D05768J | | 51 | | | | | D10690 | D2 | | | ALL |
| 15Y | 24 | | PK | 8-0 | 21-61-41 | D05768J | | 54 | | | | | D10690 | C1 | | | ALL |
| 160 | 24 | | PK | 3-0 | 29-31-11 | D04646J | | 42 | | | | | D04346J | 7 | | | ALL |
| 162 | 20 | | PA | 3-0 | 23-12-21 | D00640 | | 8 | | | | | GD0005 | D.. | 2 | | ALL |
| 163 | 24 | | PK | 3-0 | 21-53-12 | D04646J | | 45 | | | | | D04962J | 2 | | | ALL |
| 164 | 24 | | PK | 3-0 | 21-53-12 | D04646J | | 46 | | | | | D04962J | 20 | | | ALL |
| 165 | 24 | | PK | 3-0 | 21-53-12 | D04646J | | 47 | | | | | D04962J | 21 | | | ALL |
| 167 | 24 | | PK | 5-0 | 21-51-21 | D04646J | | 33 | | | | | TB0304Y | A017 | BJ | | 150-199, 275-299 |
| 168 | 24 | | PK | 5-0 | 21-51-21 | D04646J | | 34 | | | | | TB0304X | C010 | BJ | | 150-199, 275-299 |
| 169 | 24 | | PK | 5-0 | 21-26-11 | D04646J | | 50 | | | | | TB0304X | B001 | BJ | | ALL |
| 16A | 24 | | PK | 8-0 | 21-61-41 | D10690 | | B2 | | | | | D05768J | 55 | | | ALL |
| 16B | 18 | | PA | 9-0 | 33-31-41 | D03712 | | B2 | | | | | D05290J | 16 | | | ALL |
| 16C | 18 | | PA | 9-0 | 33-31-41 | D03712 | | B3 | | | | | D05290J | 14 | | | ALL |
| 16E | 24 | | PK | 3-0 | 32-09-12 | D03696 | | 10 | | | | | TB0084Y | C001 | BJ | | ALL |
| 16G | 24 | | PK | 3-0 | 32-09-12 | D03712 | | A3 | | | | | TB0084Y | C001 | BJ | | ALL |
| 16H | 24 | | PK | 5-0 | 21-61-41 | D10686 | | X2 | | | | | TB0082Y | A001 | BJ | | 050-099 |
| 16H | 24 | | PK | 3-0 | 21-61-41 | D10686 | | X2 | | | | | TB0082Y | A001 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 15

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 174 | 22 | | PA | | 9-0 | 27-81-11 | D05316J | | 28 | | D10012 | | X2 | | ALL |
| 175 | 22 | | PA | | 3-0 | 27-81-11 | D10012 | | A2 | | D01926 | | A3 | | ALL |
| 176 | 20 | | PA | | 7-0 | 32-09-12 | D03728 | | A1 | | GDX0004 | | D.. | 2 | ALL |
| 177 | 22 | | PA | | 5-0 | 21-26-21 | D01006 | | B1 | | TB0192X | | C005 | BJ | ALL |
| 178 | 24 | | PK | | 10-0 | 32-09-12 | D05316J | | 54 | | TB0084Y | | C002 | BJ | ALL |
| 17R | 24 | | PK | | 2-0 | 21-58-12 | TB0264D | | C004 | 2 | TB0264D | | C001 | 2 | 050-099, 150-199, 275-276 |
| 17S | 24 | | PK | | 2-0 | 21-58-12 | TB0264D | | C003 | 2 | TB0264D | | C002 | 2 | 050-099, 150-199, 275-276 |
| 17X | 24 | | PK | | 9-0 | 21-58-12 | TB0264D | | C001 | 2 | D08680J | | 14 | | ALL |
| 17Y | 24 | | PK | | 9-0 | 21-58-12 | TB0264D | | A001 | 2 | D06076J | | 12 | | ALL |
| 180 | 22 | | PA | | 10-0 | 73-21-19 | D05316J | | 7 | | D03730 | | A2 | | 050-099 |
| 180 | 22 | | PA | | 9-0 | 73-21-19 | D05316J | | 7 | | D03730 | | A2 | | 150-199, 275-299 |
| 181 | 24 | | PK | | 5-0 | 21-26-11 | D04646J | | 53 | | K00346 | | X2 | C | 050-099 |
| 181 | 24 | | PK | | 6-0 | 21-26-11 | D04646J | | 53 | | K00346 | | X2 | C | 150-199, 275-299 |
| 183 | 24 | | PK | | 8-0 | 21-61-31 | D04646J | | 54 | | D03754 | | X1 | | ALL |
| 184 | 22 | | PA | | 5-0 | 73-21-19 | D06260J | | 27 | | D03752 | | X1 | | 050-099, 275-299 |
| 184 | 22 | | PA | | 7-0 | 73-21-19 | D06260J | | 27 | | D03752 | | X1 | | 150-199 |
| 185 | 20 | | PQ | YF | 5-0 | 73-21-19 | D06260J | | 30 | | D03752 | | A2 | | 050-099 |
| 185 | 20 | | PQ | BI | 7-0 | 73-21-19 | D06260J | | 30 | | D03752 | | A2 | | 150-199 |
| 185 | 20 | | PQ | BI | 5-0 | 73-21-19 | D06260J | | 30 | | D03752 | | A2 | | 275-299 |
| 185Z | | | | YF | 0-0 | 73-21-19 | D06260J | | 11 | | D03752 | | | | YE 050-099 |
| 185Z | | | | BI | 0-0 | 73-21-19 | D06260J | | 11 | | D03752 | | | | YE 150-199, 275-299 |
| 188 | 24 | | PK | | 10-0 | 78-34-21 | D05316J | | 23 | | TB0084Z | | 3 | BJ | ALL |
| 189 | 24 | | PK | | 6-0 | 78-34-21 | D05316J | | 3 | | TB0274Y | | A003 | BJ | ALL |
| 18A | 22 | | PA | | 2-0 | 73-21-11 | D11756 | | Y2 | | GDX0013 | | D.. | 2 | 050-099 |
| 18A | 22 | | PA | | 3-0 | 73-21-11 | D11756 | | Y2 | | GDX0013 | | D.. | 2 | 150-199, 275-299 |
| 18B | 20 | | UA | | 2-0 | 73-21-11 | D11756 | | | | GDX0013 | | S.. | 2 | 050-099 |
| 18B | 20 | | UA | | 3-0 | 73-21-11 | D11756 | | | | GDX0013 | | S.. | 2 | 150-199, 275-299 |
| 18C | 24 | | PV | TC | 6-0 | 73-21-11 | D11756 | | A1 | | D06584J | | 9 | | 050-099 |
| 18C | 24 | | PV | BM | 7-0 | 73-21-11 | D06584J | | 9 | | D11756 | | A1 | | 150-199, 275-299 |
| 18CZ | | | | TC | 0-0 | 73-21-11 | D11756 | | | | D06584J | | | | FW 050-099 |
| 18CZ | | | | BM | 0-0 | 73-21-11 | D06584J | | | | D11756 | | | | FW 150-199, 275-299 |
| 18D | 24 | | PV | BI | 6-0 | 73-21-11 | D11756 | | A2 | | D06584J | | 10 | | 050-099 |
| 18D | 24 | | PV | BV | 7-0 | 73-21-11 | D06584J | | 10 | | D11756 | | A2 | | 150-199, 275-299 |
| 18DZ | | | | BI | 0-0 | 73-21-11 | D11756 | | | | D06584J | | | | FW 050-099 |
| 18DZ | | | | BV | 0-0 | 73-21-11 | D06584J | | | | D11756 | | | | FW 150-199, 275-299 |
| 18E | 24 | | PK | | 6-0 | 73-21-11 | D11756 | | X1 | | TB0212Z | | 16 | BJ | ALL |
| 18F | 22 | | PA | | 2-0 | 73-21-11 | D11756 | | X2 | | GDX0013 | | D.. | 2 | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 16

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 18F | 22 | | PA | | 3-0 | 73-21-11 | D11756 | | X2 | | | | GDX0013 | D.. | 2 | | 150-199, 275-299 |
| 18G | 24 | | PK | | 8-0 | 73-21-11 | D11754 | | Y1 | | | | TB0304X | A008 | BJ | | 050-099 |
| 18G | 24 | | PK | | 9-0 | 73-21-11 | D11754 | | Y1 | | | | TB0304X | A008 | BJ | | 150-199, 275-299 |
| 18H | 22 | | PA | | 2-0 | 73-21-11 | D11754 | | Y2 | | | | GDX0002 | D.. | 2 | | 050-099 |
| 18H | 22 | | PA | | 3-0 | 73-21-11 | D11754 | | Y2 | | | | GDX0002 | D.. | 2 | | 150-199, 275-299 |
| 18J | 24 | | PV | SU | 6-0 | 73-21-11 | D11754 | | A1 | | | | D06260J | 10 | | | 050-099 |
| 18J | 24 | | PV | BH | 7-0 | 73-21-11 | D11754 | | A1 | | | | D06260J | 10 | | | 150-199, 275-299 |
| 18JZ | | | | SU | 0-0 | 73-21-11 | D11754 | | | | FP | | D06260J | | | FS | 050-099 |
| 18JZ | | | | BH | 0-0 | 73-21-11 | D11754 | | | | FP | | D06260J | | | FS | 150-199, 275-299 |
| 18K | 20 | | UA | | 2-0 | 73-21-11 | D11754 | | | | FP | | GDX0002 | S.. | 2 | | 050-099 |
| 18K | 20 | | UA | | 3-0 | 73-21-11 | D11754 | | | | FP | | GDX0002 | S.. | 2 | | 150-199, 275-299 |
| 18L | 24 | | PV | ST | 6-0 | 73-21-11 | D11754 | | A2 | | | | D06260J | 31 | | | 050-099 |
| 18L | 24 | | PV | BL | 7-0 | 73-21-11 | D11754 | | A2 | | | | D06260J | 31 | | | 150-199, 275-299 |
| 18LZ | | | | ST | 0-0 | 73-21-11 | D11754 | | | | FP | | D06260J | | | FS | 050-099 |
| 18LZ | | | | BL | 0-0 | 73-21-11 | D11754 | | | | FP | | D06260J | | | FS | 150-199, 275-299 |
| 18M | 24 | | PK | | 8-0 | 73-21-11 | D11754 | | X1 | | | | TB0304X | A007 | BJ | | 050-099 |
| 18M | 24 | | PK | | 9-0 | 73-21-11 | D11754 | | X1 | | | | TB0304X | A007 | BJ | | 150-199, 275-299 |
| 18N | 22 | | PA | | 2-0 | 73-21-11 | D11754 | | X2 | | | | GDX0002 | D.. | 2 | | 050-099 |
| 18N | 22 | | PA | | 3-0 | 73-21-11 | D11754 | | X2 | | | | GDX0002 | D.. | 2 | | 150-199, 275-299 |
| 18V | 24 | | PK | | 8-0 | 21-61-81 | D13440 | | X2 | | | | D08680J | 13 | | | 050-099, 150-199 |
| 18V | 24 | | PK | | 6-0 | 21-61-81 | D13440 | | X2 | | | | D08680J | 13 | | | 275-299 |
| 192 | 20 | | PA | | 2-0 | 34-61-24 | D03684 | | 10 | | | | GDX0014 | D.. | 2 | | ALL |
| 193 | 20 | | PA | | 2-0 | 21-58-11 | D03684 | | 5 | | | | GDX0014 | D.. | 2 | | ALL |
| 194 | 24 | | PK | | 6-0 | 21-58-11 | D03684 | | 3 | | | | TB0192X | C001 | BJ | | ALL |
| 195 | 24 | | PK | | 7-0 | 32-09-12 | D03684 | | 6 | | | | TB0084Y | A008 | BJ | | ALL |
| 196 | 24 | | PK | | 3-0 | 32-09-12 | D03684 | | 12 | | | | TB0082Y | C006 | BJ | | ALL |
| 199 | 22 | | PA | | 3-0 | 27-81-11 | D10012 | | X1 | | | | TB0082G | 11 | 2 | | ALL |
| 19A | 24 | | PK | | 7-0 | 21-58-16 | D06076J | | 15 | | | | TB0088D | A006 | 2 | | 150-199, 275-299 |
| 19B | 24 | | PK | | 7-0 | 21-58-16 | D06076J | | 7 | | | | TB0088D | A010 | 2 | | 150-199, 275-299 |
| 19C | 24 | | PK | | 2-0 | 21-58-16 | TB0088D | | C006 | 2 | | | TB0088D | C010 | 2 | | 150-199, 275-299 |
| 19E | 24 | | PK | | 3-0 | 21-58-16 | D10892 | | B1 | | | | TB0088D | C010 | 2 | | 150-199, 275-299 |
| 19F | 24 | | PK | | 9-0 | 21-58-12 | D06076J | | 13 | | | | TB0264D | C002 | 2 | | ALL |
| 19G | 24 | | PK | | 9-0 | 21-58-12 | D06076J | | 14 | | | | TB0264D | A002 | 2 | | ALL |
| 19H | 24 | | PK | | 2-0 | 21-58-12 | TB0264D | | A003 | 2 | | | TB0264D | A004 | 2 | | 050-099, 150-199, 275-276 |
| 19J | 24 | | PK | | 7-0 | 21-45-21 | TB0192X | | A001 | BJ | | | TB0084D | A015 | 2 | | ALL |
| 19K | 24 | | PK | | 2-0 | 21-45-21 | TB0084D | | A016 | 2 | | | TB0084D | A015 | 2 | | ALL |
| 19L | 24 | | PK | | 2-0 | 21-45-21 | TB0084D | | A016 | 2 | | | TB0264D | A008 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 17

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 19M | 24 | | PK | 2-0 | 21-45-21 | TB0084D | C015 | 2 | | TB0264D | C004 | 2 | | 050-099, 150-199, 275-276 | |
| 19M | 24 | | PK | 2-0 | 21-45-21 | TB0084D | C015 | 2 | | TB0264D | C001 | 2 | | 277-299 | |
| 19N | 24 | | PK | 2-0 | 21-45-21 | TB0084D | C016 | 2 | | TB0264D | C003 | 2 | | 050-099, 150-199, 275-276 | |
| 19N | 24 | | PK | 2-0 | 21-45-21 | TB0084D | C016 | 2 | | TB0264D | C002 | 2 | | 277-299 | |
| 19P | 24 | | PK | 7-0 | 21-45-21 | TB0192Y | C012 | BJ | | TB0264D | C008 | 2 | | ALL | |
| 19R | 24 | | PK | 6-0 | 21-25-21 | D04646J | | 22 | | TB0192Y | C012 | BJ | | ALL | |
| 19U | 16 | | PA | 11-0 | 38-13-11 | D05660J | | 11 | | C01373 | | D | | 050-099 | |
| 19U | 16 | | PA | 9-0 | 38-13-11 | C01373 | | 2 | D | TB0210G | | 8 | 2 | 150-157 | |
| 19W | 20 | | PA | 2-0 | 21-58-16 | D10892 | | B2 | | GD0003 | | D.. | 2 | 150-199, 275-299 | |
| 19X | 24 | | PK | 8-0 | 73-21-18 | D04646J | | 52 | | D13532 | | 12 | | 050-099 | |
| 19X | 24 | | PK | 9-0 | 73-21-18 | D04646J | | 52 | | D13532 | | 12 | | 150-199, 275-299 | |
| 19Y | 24 | | PK | 10-0 | 73-21-18 | D13532 | | 6 | | TB0320Y | A020 | BJ | | 050-099 | |
| 19Y | 24 | | PK | 10-0 | 73-21-18 | TB0320Y | A020 | BJ | | D13532 | | 6 | | 150-154 | |
| 19Y | 24 | | PK | 9-0 | 73-21-18 | TB0320Y | A020 | BJ | | D13532 | | 6 | | 155-199 | |
| 19Y | 24 | | PK | 10-0 | 73-21-18 | TB0320Y | A020 | BJ | | D03532 | | 6 | | 275-276 | |
| 19Y | 24 | | PK | 9-0 | 73-21-18 | D13532 | | 6 | | TB0320Y | A020 | BJ | | 277-299 | |
| 201B | 24 | | PL | H | 8-0 | 21-31-21 | D05612J | | 60 | D03696 | | 8 | | ALL | |
| 201R | 24 | | PL | H | 0-0 | 21-31-21 | D05612J | | 61 | D03696 | | 7 | | ALL | |
| 203B | 24 | | PW | AB | 6-0 | 31-31-12 | D05437J | | 24 | D01644 | | 1 | | ALL | |
| 203R | 24 | | PW | AB | 0-0 | 31-31-12 | D05437J | | 23 | D01644 | | 5 | | ALL | |
| 203Z | | | | AB | 0-0 | 31-31-12 | D05437J | | 25 | D01644 | | | FF | ALL | |
| 204B | 24 | | PW | AC | 6-0 | 31-31-12 | D05435J | | 28 | D01644 | | 6 | | ALL | |
| 204R | 24 | | PW | AC | 0-0 | 31-31-12 | D05435J | | 29 | D01644 | | 2 | | ALL | |
| 204Z | | | | AC | 0-0 | 31-31-12 | D05435J | | 36 | D01644 | | | FG | ALL | |
| 205B | 24 | | PW | AA | 6-0 | 31-31-12 | D05437J | | 21 | D01644 | | 8 | | ALL | |
| 205R | 24 | | PW | AA | 0-0 | 31-31-12 | D05437J | | 20 | D01644 | | 4 | | ALL | |
| 205Z | | | | AA | 0-0 | 31-31-12 | D05437J | | 22 | D01644 | | | FE | ALL | |
| 206B | 22 | | PB | AH | 4-0 | 21-61-51 | D05768J | | 4 | TB0304X | A004 | BJ | | ALL | |
| 206R | 22 | | PB | AH | 0-0 | 21-61-51 | D05768J | | 5 | TB0304X | B004 | BJ | | ALL | |
| 208B | 22 | | PB | J | 4-0 | 27-51-41 | D05316J | | 17 | TB0304X | B006 | BJ | | ALL | |
| 208R | 22 | | PB | J | 0-0 | 27-51-41 | D05316J | | 18 | TB0304X | A006 | BJ | | ALL | |
| 209B | 24 | | PL | L | 9-0 | 21-51-22 | D04004J | | 18 | D03694 | | 13 | | ALL | |
| 209R | 24 | | PL | L | 0-0 | 21-51-22 | D04004J | | 19 | D03694 | | 1 | | ALL | |
| 20B | 20 | | PA | | 8-0 | 29-11-14 | TB0274D | | A041 | TB0088D | A012 | 2 | | ALL | |
| 20C | 20 | | PA | | 8-0 | 29-11-14 | TB0192Z | | 17 | TB0088D | C012 | 2 | | 050-099 | |
| 20C | 20 | | PA | | 8-0 | 29-11-14 | TB0088D | | C012 | TB0192Z | | 17 | BJ | 150-199, 275-299 | |
| 20D | 20 | | PA | | 5-0 | 29-11-14 | D13021 | | A3 | TB0192X | B009 | BJ | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W0190
Page 18
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 20E | 20 | | PA | 9-0 | 29-11-14 | D13021 | | A2 | | | | | TB0088D | A012 | 2 | | ALL |
| 20F | 24 | | PK | 6-0 | 21-61-81 | D08680J | | 2 | | | | | D13438 | B2 | | | 050-099 |
| 20F | 24 | | PK | 7-0 | 21-61-81 | D13438 | | B2 | | | | | D08680J | 2 | | | 150-199 |
| 20F | 24 | | PK | 8-0 | 21-61-81 | D13438 | | B2 | | | | | D08680J | 2 | | | 275-299 |
| 20G | 24 | | PK | 6-0 | 21-61-81 | D08680J | | 3 | | | | | D13438 | B1 | | | 050-099 |
| 20G | 24 | | PK | 7-0 | 21-61-81 | D13438 | | B1 | | | | | D08680J | 3 | | | 150-199 |
| 20G | 24 | | PK | 8-0 | 21-61-81 | D13438 | | B1 | | | | | D08680J | 3 | | | 275-299 |
| 20HB | 24 | | PL | DL | 8-0 | 21-61-81 | D08680J | | 5 | | | | D13440 | A1 | | | 050-099 |
| 20HB | 24 | | PL | DL | 8-0 | 21-61-81 | D13440 | | A1 | | | | D08680J | 5 | | | 150-199, 275-299 |
| 20HR | 24 | | PL | DL | 0-0 | 21-61-81 | D08680J | | 4 | | | | D13440 | B1 | | | 050-099 |
| 20HR | 24 | | PL | DL | 0-0 | 21-61-81 | D13440 | | B1 | | | | D08680J | 4 | | | 150-199, 275-299 |
| 20J | 24 | | PK | | 8-0 | 21-61-81 | D08680J | | 6 | | | | D13440 | D3 | | | 050-099 |
| 20J | 24 | | PK | | 8-0 | 21-61-81 | D13440 | | D3 | | | | D08680J | 6 | | | 150-199, 275-299 |
| 20K | 24 | | PK | | 5-0 | 21-61-81 | D08680J | | 7 | | | | TB0304Y | A013 | BJ | | 050-099 |
| 20K | 24 | | PK | | 5-0 | 21-61-81 | TB0304Y | | A013 | BJ | | | D08680J | 7 | | | 150-199 |
| 20K | 24 | | PK | | 6-0 | 21-61-81 | TB0304Y | | A013 | BJ | | | D08680J | 7 | | | 275-299 |
| 20L | 24 | | PK | | 8-0 | 21-61-81 | D08680J | | 8 | | | | D13440 | A2 | | | 050-099 |
| 20L | 24 | | PK | | 8-0 | 21-61-81 | D13440 | | A2 | | | | D08680J | 8 | | | 150-199, 275-299 |
| 20S | 24 | | PK | | 8-0 | 21-61-81 | D05602J | | 10 | | | | D13438 | X2 | | | 050-099 |
| 20S | 24 | | PK | | 8-0 | 21-61-81 | D13438 | | X2 | | | | D05602J | 10 | | | 150-199, 275-299 |
| 20U | 22 | | PA | | 10-0 | 21-26-31 | D06076J | | 1 | | | | TB0304Y | C024 | BJ | | 050-099 |
| 20U | 22 | | PA | | 6-0 | 21-26-31 | D06076J | | 1 | | | | TB0304Y | C024 | BJ | | 150-199 |
| 20U | 22 | | PA | | 6-0 | 21-26-31 | D06076J | | 1 | | | | TB0304X | B002 | BJ | | 275-299 |
| 210B | 24 | | PL | M | 4-0 | 36-21-11 | TB0304Y | | C034 | BJ | | | D04284J | 28 | | | 050-099 |
| 210B | 24 | | PL | M | 5-0 | 36-21-11 | TB0304Y | | C034 | BJ | | | D04284J | 28 | | | 150-199 |
| 210B | 24 | | PL | M | 3-0 | 36-21-11 | TB0304Y | | C034 | BJ | | | D04284J | 28 | | | 275-299 |
| 210R | 24 | | PL | M | 0-0 | 36-21-11 | TB0304Y | | A034 | BJ | | | D04284J | 27 | | | ALL |
| 214B | 24 | | PW | CW | 5-0 | 34-61-25 | D01725 | | B3 | | | | D05499J | 2 | | | ALL |
| 214R | 24 | | PW | CW | 0-0 | 34-61-25 | D01725 | | A3 | | | | D05499J | 3 | | | ALL |
| 214Z | | | | CW | 0-0 | 34-61-25 | D01725 | | DED | | | | D05499J | 4 | | | ALL |
| 215B | 24 | | PW | CU | 5-0 | 34-61-25 | D01725 | | B1 | | | | D05499J | 5 | | | ALL |
| 215R | 24 | | PW | CU | 0-0 | 34-61-25 | D01725 | | A1 | | | | D05499J | 6 | | | ALL |
| 215Z | | | | CU | 0-0 | 34-61-25 | D01725 | | DED | | | | D05499J | 7 | | | ALL |
| 216B | 24 | | PW | CV | 5-0 | 34-61-25 | D01725 | | B2 | | | | D05499J | 8 | | | ALL |
| 216R | 24 | | PW | CV | 0-0 | 34-61-25 | D01725 | | A2 | | | | D05499J | 9 | | | ALL |
| 216Z | | | | CV | 0-0 | 34-61-25 | D01725 | | DED | | | | D05499J | 10 | | | ALL |
| 218B | 22 | | PB | U | 3-0 | 27-81-21 | D05316J | | 12 | | | | D04962J | 36 | | | ALL |
| 218R | 22 | | PB | U | 0-0 | 27-81-21 | D05316J | | 13 | | | | D04962J | 35 | | | ALL |
| 21F | 24 | | PK | | 5-0 | 77-35-11 | TB0212Y | | A013 | BJ | | | D05437J | 6 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 19

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|--------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 21F | 24 | | PK | | 7-0 77-35-11 | D05437J | | 6 | | | | | TB0212Y | A013 | BJ | | 150-199, 275-299 |
| 21G | 24 | | PK | | 5-0 77-35-11 | TB0212Y | | A013 | BJ | | | | D05316J | 60 | | | 050-099 |
| 21G | 24 | | PK | | 7-0 77-35-11 | D05316J | | 60 | | | | | TB0212Y | A013 | BJ | | 150-199, 275-299 |
| 21K | 24 | | PK | | 7-0 24-11-21 | D05316J | | 59 | | | | | D11796 | 13 | | | ALL |
| 21L | 20 | | PA | | 3-0 24-11-21 | GDX0003 | | D.. | 2 | | | | D11796 | 12 | | | 050-099 |
| 21L | 24 | | PK | | 4-0 24-11-21 | GDX0003 | | D.. | 2 | | | | D11796 | 12 | | | 150-199 |
| 21L | 20 | | PA | | 7-0 24-11-21 | GDX0003 | | D.. | 2 | | | | D11796 | 12 | | | 275-299 |
| 21M | 24 | | PK | | 7-0 24-11-21 | TB0304R | | C032 | 2 | | | | D11796 | 1 | | | 050 |
| 21M | 24 | | PK | | 7-0 24-11-21 | D05374J | | 35 | | | | | D11796 | 1 | | | 051-099 |
| 21M | 24 | | PK | | 8-0 24-11-21 | D11796 | | 1 | | | | | TB0304R | C032 | 2 | | 150, 152-199 |
| 21M | 24 | | PK | | 8-0 24-11-21 | D11796 | | 1 | | | | | TB0304R | C032 | 2 | * | 151 |
| 21M | 24 | | PK | | 8-0 24-11-21 | D11796 | | 1 | | | | | D05374J | 35 | | | 275-299 |
| 21N | 24 | | PK | | 7-0 24-11-21 | D05316J | | 61 | | | | | D11796 | 6 | | | ALL |
| 21P | 24 | | PK | | 7-0 24-11-21 | D05316J | | 51 | | | | | D11796 | 2 | | | ALL |
| 224B | 24 | | PW | AE | 6-0 32-42-11 | D04004J | | 23 | | | | | TB0190Y | C016 | BJ | | ALL |
| 224R | 24 | | PW | AE | 0-0 32-42-11 | D04004J | | 24 | | | | | TB0190Y | A016 | BJ | | ALL |
| 224Z | | | | AE | 0-0 32-42-11 | D04004J | | 2 | | | | | TB0190Y | C015 | BJ | | ALL |
| 225B | 24 | | PW | AF | 4-0 73-21-14 | D05316J | | 46 | | | | | TB0304Z | 21 | BJ | | ALL |
| 225R | 24 | | PW | AF | 0-0 73-21-14 | D05316J | | 39 | | | | | TB0304Z | 22 | BJ | | ALL |
| 225Z | | | | AF | 0-0 73-21-14 | D05316J | | | | | FH | | TB0304Y | A019 | BJ | | 050-099 |
| 225Z | | | | AF | 0-0 73-21-14 | D05316J | | | | | FY | | TB0304Y | A019 | BJ | | 150-199, 275-299 |
| 226B | 24 | | PW | JA | 4-0 73-21-14 | D05266J | | 3 | | | | | TB0304Z | 21 | BJ | | 050-099 |
| 226B | 24 | | PW | CM | 5-0 73-21-14 | TB0304Z | | 21 | BJ | | | | D05266J | 3 | | | 150-199, 275-299 |
| 226R | 24 | | PW | JA | 0-0 73-21-14 | D05266J | | 4 | | | | | TB0304Z | 22 | BJ | | 050-099 |
| 226R | 24 | | PW | CM | 0-0 73-21-14 | TB0304Z | | 22 | BJ | | | | D05266J | 4 | | | 150-199, 275-299 |
| 226Z | | | | JA | 0-0 73-21-14 | D05266J | | 5 | | | | | TB0304Y | A019 | BJ | | 050-099 |
| 226Z | | | | CM | 0-0 73-21-14 | TB0304Y | | A019 | BJ | | | | D05266J | 5 | | | 150-199, 275-299 |
| 22A | 22 | | PA | | 5-0 36-11-62 | D01724 | | B1 | | | | | TB0254G | 13 | 2 | | 050-099, 155-156, 166 |
| 22A | 22 | | PA | | 4-0 36-11-62 | D01724 | | B1 | | | | | TB0254G | 13 | 2 | | 150-154, 162-165, 275-276 |
| 22R | 22 | | PA | | 7-0 32-45-11 | D13532 | | 13 | | | | | TB0274X | C013 | BJ | | 050-099 |
| 22R | 22 | | PA | | 8-0 32-45-11 | TB0274X | | C013 | BJ | | | | D13532 | 13 | | | 150-199, 275-299 |
| 22S | 22 | | PA | | 7-0 32-45-11 | D13532 | | 1 | | | | | TB0274X | B013 | BJ | | 050-099 |
| 22S | 22 | | PA | | 8-0 32-45-11 | TB0274X | | B013 | BJ | | | | D13532 | 1 | | | 150-199, 275-299 |
| 22VB | 22 | | PB | BK | 9-0 21-61-81 | D12208 | | A1 | | | | | TB0320R | C031 | 2 | | 050-099 |
| 22VB | 22 | | PB | BK | 8-0 21-61-81 | D12208 | | A1 | | | | | TB0320R | C031 | BJ | | 151-154 |
| 22VB | 22 | | PB | BK | 8-0 21-61-81 | D12208 | | A1 | | | | | TB0320R | C031 | 2 | | 155-199, 275-299 |
| 22VR | 22 | | PB | BK | 0-0 21-61-81 | D12208 | | A2 | | | | | TB0320F | A030 | 2 | | 050-099, 155-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 20

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | |
| 22VR | 22 | PB | BK | 0-0 | 21-61-81 | D12208 | | A2 | | | | TB0320F | A030 | BJ | | 151-154 |
| 22WB | 22 | PB | DO | 9-0 | 21-61-81 | D12208 | | B1 | | | | TB0320R | C029 | 2 | | 050-099 |
| 22WB | 22 | PB | DO | 8-0 | 21-61-81 | D12208 | | B1 | | | | TB0320R | C029 | BJ | | 151-154 |
| 22WB | 22 | PB | DO | 8-0 | 21-61-81 | D12208 | | B1 | | | | TB0320R | C029 | 2 | | 155-199, 275-299 |
| 22WR | 22 | PB | DO | 0-0 | 21-61-81 | D12208 | | B2 | | | | TB0320F | C030 | 2 | | 050-099, 155-199, 275-299 |
| 22WR | 22 | PB | DO | 0-0 | 21-61-81 | D12208 | | B2 | | | | TB0320F | C030 | BJ | | 151-154 |
| 22XB | 22 | PB | DX | 4-0 | 21-61-81 | D08680J | | 21 | | | | TB0320R | A029 | 2 | | 050-099 |
| 22XB | 22 | PB | DX | 5-0 | 21-61-81 | D08680J | | 21 | | | | TB0320R | A029 | BJ | | 151-154 |
| 22XB | 22 | PB | DX | 5-0 | 21-61-81 | D08680J | | 21 | | | | TB0320R | A029 | 2 | | 155-199, 275-299 |
| 22XR | 22 | PB | DX | 0-0 | 21-61-81 | D08680J | | 20 | | | | TB0320F | C030 | 2 | | 050-099, 155-199, 275-299 |
| 22XR | 22 | PB | DX | 0-0 | 21-61-81 | D08680J | | 20 | | | | TB0320F | C030 | BJ | | 151-154 |
| 22YB | 22 | PB | DY | 4-0 | 21-61-81 | D08680J | | 23 | | | | TB0320R | A031 | 2 | | 050-099 |
| 22YB | 22 | PB | DY | 5-0 | 21-61-81 | D08680J | | 23 | | | | TB0320R | A031 | BJ | | 151-154 |
| 22YB | 22 | PB | DY | 5-0 | 21-61-81 | D08680J | | 23 | | | | TB0320R | A031 | 2 | | 155-199, 275-299 |
| 22YR | 22 | PB | DY | 0-0 | 21-61-81 | D08680J | | 22 | | | | TB0320F | A030 | 2 | | 050-099, 155-199, 275-299 |
| 22YR | 22 | PB | DY | 0-0 | 21-61-81 | D08680J | | 22 | | | | TB0320F | A030 | BJ | | 151-154 |
| 230B | 22 | PB | BF | 3-0 | 32-61-13 | D04646J | | 26 | | | | D05592J | 2 | | | ALL |
| 230R | 22 | PB | BF | 0-0 | 32-61-13 | D04646J | | 25 | | | | D05592J | 1 | | | ALL |
| 231B | 22 | PB | BG | 3-0 | 32-61-13 | D04646J | | 28 | | | | D05592J | 4 | | | ALL |
| 231R | 22 | PB | BG | 0-0 | 32-61-13 | D04646J | | 27 | | | | D05592J | 3 | | | ALL |
| 232B | 22 | PB | BA | 3-0 | 32-61-13 | D04646J | | 30 | | | | D05592J | 6 | | | ALL |
| 232R | 22 | PB | BA | 0-0 | 32-61-13 | D04646J | | 29 | | | | D05592J | 5 | | | ALL |
| 233B | 22 | PB | BB | 3-0 | 32-61-13 | D04646J | | 32 | | | | D05592J | 8 | | | ALL |
| 233R | 22 | PB | BB | 0-0 | 32-61-13 | D04646J | | 31 | | | | D05592J | 7 | | | ALL |
| 236B | 24 | PW | BD | 5-0 | 32-42-11 | D00666 | | B1 | | | | TB0190Y | C016 | BJ | | ALL |
| 236R | 24 | PW | BD | 0-0 | 32-42-11 | D00666 | | A1 | | | | TB0190Y | A016 | BJ | | ALL |
| 236Z | | | BD | 0-0 | 32-42-11 | D00666 | | | | AA | | TB0190Y | C015 | BJ | | ALL |
| 237B | 24 | PW | BE | 5-0 | 32-42-11 | D00666 | | B3 | | | | D05435J | 41 | | | ALL |
| 237R | 24 | PW | BE | 0-0 | 32-42-11 | D00666 | | A3 | | | | D05435J | 40 | | | ALL |
| 237Z | | | BE | 0-0 | 32-42-11 | D00666 | | | | AA | | D05435J | 42 | | | ALL |
| 238B | 24 | PW | P | 5-0 | 32-42-11 | D00666 | | B2 | | | | TB0274Y | C039 | BJ | | 050-099 |
| 238B | 24 | PW | P | 6-0 | 32-42-11 | D00666 | | B2 | | | | TB0274Y | C039 | BJ | | 150-199, 275-299 |
| 238R | 24 | PW | P | 0-0 | 32-42-11 | D00666 | | A2 | | | | TB0274Y | A039 | BJ | | ALL |
| 238Z | | | P | 0-0 | 32-42-11 | D00666 | | | | AA | | TB0274Y | A040 | BJ | | ALL |
| 239B | 24 | PL | Q | 3-0 | 32-09-12 | D05592J | | 16 | | | | D05612J | 28 | | | ALL |
| 239R | 24 | PL | Q | 0-0 | 32-09-12 | D05592J | | 15 | | | | D05612J | 26 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 21

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 240B | 22 | PB | A | 3-0 | 21-51-13 | D04962J | | 10 | | | D05352J | | 1 | | ALL |
| 240R | 22 | PB | A | 0-0 | 21-51-13 | D04962J | | 31 | | | D05352J | | 25 | | ALL |
| 241B | 22 | PB | R | 3-0 | 21-51-13 | D04962J | | 26 | | | D05352J | | 38 | | ALL |
| 241R | 22 | PB | R | 0-0 | 21-51-13 | D04962J | | 29 | | | D05352J | | 39 | | ALL |
| 244B | 20 | PB | DN | 4-0 | 36-22-21 | D04346J | | 53 | | | D05374J | | 49 | | 050-099 |
| 244B | 20 | PB | DN | 4-0 | 36-22-21 | D05374J | | 49 | | | D04346J | | 53 | | 150-199, 275-299 |
| 244R | 20 | PB | DN | 0-0 | 36-22-21 | D04346J | | 52 | | | D05374J | | 50 | | 050-099 |
| 244R | 20 | PB | DN | 0-0 | 36-22-21 | D05374J | | 50 | | | D04346J | | 52 | | 150-199, 275-299 |
| 245B | 24 | PL | AJ | 8-0 | 21-61-21 | D05612J | | 49 | | | D03716 | | B3 | | ALL |
| 245R | 24 | PL | AJ | 0-0 | 21-61-21 | D05612J | | 50 | | | D03716 | | C3 | | ALL |
| 246B | 24 | PL | AN | 8-0 | 21-61-31 | D04646J | | 57 | | | D03754 | | B3 | | ALL |
| 246R | 24 | PL | AN | 0-0 | 21-61-31 | D04646J | | 58 | | | D03754 | | C3 | | ALL |
| 247B | 24 | PL | AD | 4-0 | 29-31-11 | D04346J | | 4 | | | D05374J | | 13 | | ALL |
| 247R | 24 | PL | AD | 0-0 | 29-31-11 | D04346J | | 8 | | | D05374J | | 12 | | ALL |
| 248B | 24 | PW | JW | 6-0 | 27-32-21 | TB0274Y | | C039 | BJ | | D05435J | | 50 | | ALL |
| 248R | 24 | PW | JW | 0-0 | 27-32-21 | TB0274Y | | A039 | BJ | | D05435J | | 49 | | ALL |
| 248Z | | | JW | 0-0 | 27-32-21 | TB0274Y | | A040 | BJ | | D05435J | | 44 | | ALL |
| 249B | 24 | PW | JX | 4-0 | 73-21-14 | D05316J | | 32 | | | TB0304Y | A018 | BJ | | 050-099 |
| 249B | 24 | PW | AR | 4-0 | 73-21-14 | D05316J | | 32 | | | TB0304Y | A018 | BJ | | 150-199, 275-299 |
| 249R | 24 | PW | JX | 0-0 | 73-21-14 | D05316J | | 53 | | | TB0304Y | C018 | BJ | | 050-099 |
| 249R | 24 | PW | AR | 0-0 | 73-21-14 | D05316J | | 53 | | | TB0304Y | C018 | BJ | | 150-199, 275-299 |
| 249Z | | | JX | 0-0 | 73-21-14 | D05316J | | | | FH | TB0304Y | A020 | BJ | | 050-099 |
| 249Z | | | AR | 0-0 | 73-21-14 | D05316J | | | | FY | TB0304Y | A020 | BJ | | 150-199, 275-299 |
| 24A | 22 | PA | | 10-0 | 36-11-62 | TB0314Y | | A004 | BJ | | D06076J | | 20 | | ALL |
| 24NB | 24 | PW | BY | 4-0 | 31-35-15 | D05435J | | 19 | | | D06584J | | 17 | | 050-099 |
| 24NB | 24 | PW | EA | 4-0 | 31-35-15 | D05435J | | 19 | | | D06584J | | 17 | | 150-199, 275-276, 278-299 |
| 24NR | 24 | PW | BY | 0-0 | 31-35-15 | D05435J | | 18 | | | D06584J | | 16 | | 050-099 |
| 24NR | 24 | PW | EA | 0-0 | 31-35-15 | D05435J | | 18 | | | D06584J | | 16 | | 150-199, 275-276, 278-299 |
| 24NZ | | | BY | 0-0 | 31-35-15 | D05435J | | 20 | | | D06584J | | 18 | | 050-099 |
| 24NZ | | | EA | 0-0 | 31-35-15 | D05435J | | 20 | | | D06584J | | 18 | | 150-199, 275-276, 278-299 |
| 24P | 20 | PA | | 10-0 | 78-34-21 | D20104 | | X2 | | | GDX0016 | D.. | 2 | | ALL |
| 24Q | 22 | PQ | FY | 12-0 | 78-34-21 | D20104 | | X1 | | | D04284J | | 31 | | ALL |
| 24QZ | | | FY | 0-0 | 78-34-21 | D20104 | | DED | | | D04284J | | 32 | | ALL |
| 24R | 20 | PQ | HJ | 8-0 | 78-34-21 | D20104 | | A2 | | | TB0084Z | | 14 | BJ | ALL |
| 24RZ | | | HJ | 0-0 | 78-34-21 | D20104 | | DED | | | TB0084Z | | | | HM ALL |
| 24T | 24 | PK | | 5-0 | 78-34-21 | D20104 | | B1 | | | TB0084Z | | 14 | BJ | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 22

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 24T | 22 | | PA | 5-0 | 78-34-21 | D20104 | | B1 | | | | | TB0084Z | 14 | BJ | | 150-199, 275-299 |
| 24V | 20 | | PQ | 12-0 | 78-34-21 | D05326J | | 45 | | | | | D20104 | A1 | | | ALL |
| 24VZ | | | HI | 0-0 | 78-34-21 | D05326J | | | | | | | D20104 | DED | | | ALL |
| 251B | 24 | | PW | 4-0 | 73-21-14 | D06260J | | 24 | | | | | TB0304Y | A018 | BJ | | 050-099 |
| 251B | 24 | | PW | 4-0 | 73-21-14 | D06260J | | 24 | | | | | TB0304Y | A018 | BJ | | 150-199, 275-299 |
| 251R | 24 | | PW | 0-0 | 73-21-14 | D06260J | | 25 | | | | | TB0304Y | C018 | BJ | | 050-099 |
| 251R | 24 | | PW | 0-0 | 73-21-14 | D06260J | | 25 | | | | | TB0304Y | C018 | BJ | | 150-199, 275-299 |
| 251Z | | | KA | 0-0 | 73-21-14 | D06260J | | 26 | | | | | TB0304Y | A020 | BJ | | 050-099 |
| 251Z | | | AT | 0-0 | 73-21-14 | D06260J | | 26 | | | | | TB0304Y | A020 | BJ | | 150-199, 275-299 |
| 252B | 24 | | PW | 4-0 | 73-21-14 | D05326J | | 42 | | | | | TB0304Y | A018 | BJ | | ALL |
| 252R | 24 | | PW | 0-0 | 73-21-14 | D05326J | | 43 | | | | | TB0304Y | C018 | BJ | | ALL |
| 252Z | | | BT | 0-0 | 73-21-14 | D05326J | | 41 | | | | | TB0304Y | A020 | BJ | | ALL |
| 254B | 24 | | PW | 3-0 | 73-21-14 | D05374J | | 26 | | | | | TB0304Y | A018 | BJ | | ALL |
| 254R | 24 | | PW | 0-0 | 73-21-14 | D05374J | | 27 | | | | | TB0304Y | C018 | BJ | | ALL |
| 254Z | | | AW | 0-0 | 73-21-14 | D05374J | | 20 | | | | | TB0304Y | A020 | BJ | | ALL |
| 25A | 20 | | PA | 2-0 | 21-26-11 | D03788 | | B1 | | | | | GDY0005 | D.. | 2 | | 156-157, 166-199, 277-299 |
| 262B | 24 | | PL | 4-0 | 21-51-21 | TB0304X | | A010 | BJ | | | | D05352J | 26 | | | ALL |
| 262R | 24 | | PL | 0-0 | 21-51-21 | TB0304X | | B010 | BJ | | | | D05352J | 27 | | | ALL |
| 263B | 24 | | PL | 7-0 | 28-41-11 | D03690 | | 5 | | | | | TB0212X | B003 | BJ | | ALL |
| 263R | 24 | | PL | 0-0 | 28-41-11 | D03690 | | 3 | | | | | TB0212X | A003 | BJ | | ALL |
| 267B | 24 | | PW | 3-0 | 73-21-14 | D05316J | | 47 | | | | | D06584J | 27 | | | 050-099 |
| 267B | 24 | | PW | 4-0 | 73-21-14 | D05316J | | 47 | | | | | D06584J | 27 | | | 150-199 |
| 267B | 24 | | PW | 6-0 | 73-21-14 | D05316J | | 47 | | | | | D06584J | 27 | | | 275-299 |
| 267R | 24 | | PW | 0-0 | 73-21-14 | D05316J | | 26 | | | | | D06584J | 28 | | | ALL |
| 267Z | | | EC | 0-0 | 73-21-14 | D05316J | | | | | | | D06584J | | | | 050-099 |
| 267Z | | | EC | 0-0 | 73-21-14 | D05316J | | | | | | | D06584J | | | | 150-199, 275-299 |
| 268B | 24 | | PW | 5-0 | 73-21-14 | TB0304Z | | 21 | BJ | | | | D06584J | 25 | | | 050-099, 275-299 |
| 268B | 24 | | PW | 6-0 | 73-21-14 | TB0304Z | | 21 | BJ | | | | D06584J | 25 | | | 150-199 |
| 268R | 24 | | PW | 0-0 | 73-21-14 | TB0304Z | | 22 | BJ | | | | D06584J | 26 | | | ALL |
| 268Z | | | ED | 0-0 | 73-21-14 | TB0304Y | | A019 | BJ | | | | D06584J | | | | 050-099 |
| 268Z | | | ED | 0-0 | 73-21-14 | TB0304Y | | A019 | BJ | | | | D06584J | | | | 150-199, 275-299 |
| 26A | 22 | | PA | 10-0 | 36-11-62 | TB0254G | | 13 | 2 | | | | TB0314Y | C004 | BJ | | 050-099, 150-156, 162-166, 275-276 |
| 270B | 24 | | PL | 8-0 | 21-61-41 | D10690 | | B3 | | | | | D05768J | 52 | | | ALL |
| 270R | 24 | | PL | 0-0 | 21-61-41 | D10690 | | C3 | | | | | D05768J | 53 | | | ALL |
| 273B | 20 | | PR | 6-0 | 32-45-12 | D05592J | | 17 | | | | | TB0210X | B017 | BJ | | 050-099, 150-199 |
| 273B | 20 | | PR | 4-0 | 32-45-12 | D05592J | | 17 | | | | | TB0320X | D035 | BJ | | 275-299 |
| 273R | 20 | | PR | 0-0 | 32-45-12 | D05592J | | 18 | | | | | TB0210X | A017 | BJ | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 23

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 273R | 20 | PR | KW | 0-0 | 32-45-12 | D05592J | | 18 | | | TB0320X | C035 | BJ | | 275-299 |
| 273Z | | | AP | 0-0 | 32-45-12 | D05592J | | 14 | | | TB0210X | C017 | BJ | | 050-099 |
| 273Z | | | AP | 0-0 | 32-45-12 | TB0210X | | | C017 | BJ | D05592J | | 14 | | 150-199 |
| 273Z | | | KW | 0-0 | 32-45-12 | D05592J | | 14 | | | TB0320X | A036 | BJ | | 275-299 |
| 274B | 22 | PR | FB | 3-0 | 21-66-41 | D05318J | | 22 | | | D05290J | | 23 | | 050-099, 150, 152-199 |
| 274R | 22 | PR | FB | 0-0 | 21-66-41 | D05318J | | 21 | | | D05290J | | 25 | | 050-099, 150, 152-199 |
| 274Z | | | FB | 0-0 | 21-66-41 | D05318J | | 23 | | | D05290J | | 21 | | 050-099, 150, 152-199 |
| 275B | 24 | PL | AM | 5-0 | 36-21-11 | D04004J | | 17 | | | TB0304Y | C034 | BJ | | 050-099 |
| 275B | 24 | PL | DI | 6-0 | 36-21-11 | TB0304Y | | | C034 | BJ | D04004J | | 17 | | 150-155, 157, 163-165, 167-199 |
| 275B | 24 | PL | KY | 4-0 | 36-21-11 | TB0304Y | | | C034 | BJ | D04004J | | 17 | | 156, 166 |
| 275B | 24 | PL | KY | 6-0 | 36-21-11 | TB0304Y | | | C034 | BJ | D04004J | | 17 | | 162 |
| 275B | 24 | PL | AM | 4-0 | 36-21-11 | D04004J | | 17 | | | TB0304Y | C034 | BJ | | 275-278 |
| 275B | 24 | PL | KY | 4-0 | 36-21-11 | D04004J | | 17 | | | TB0304Y | C034 | BJ | | 280-299 |
| 275R | 24 | PL | AM | 0-0 | 36-21-11 | D04004J | | 16 | | | TB0304Y | A034 | BJ | | 050-099, 275-278 |
| 275R | 24 | PL | DI | 0-0 | 36-21-11 | TB0304Y | | | A034 | BJ | D04004J | | 16 | | 150-155, 157, 163-165, 167-199 |
| 275R | 24 | PL | KY | 0-0 | 36-21-11 | TB0304Y | | | A034 | BJ | D04004J | | 16 | | 156, 162, 166 |
| 275R | 24 | PL | KY | 0-0 | 36-21-11 | D04004J | | 16 | | | TB0304Y | A034 | BJ | | 280-299 |
| 276B | 24 | PL | AO | 5-0 | 36-21-11 | D04004J | | 31 | | | TB0304Y | C034 | BJ | | 050-099 |
| 276B | 24 | PL | DJ | 6-0 | 36-21-11 | TB0304Y | | | C034 | BJ | D04004J | | 31 | | 150-155, 157, 163-165, 167-199 |
| 276B | 24 | PL | LA | 4-0 | 36-21-11 | TB0304Y | | | C034 | BJ | D04004J | | 31 | | 156, 166 |
| 276B | 24 | PL | LA | 6-0 | 36-21-11 | TB0304Y | | | C034 | BJ | D04004J | | 31 | | 162 |
| 276B | 24 | PL | AO | 4-0 | 36-21-11 | D04004J | | 31 | | | TB0304Y | C034 | BJ | | 275-278 |
| 276B | 24 | PL | LA | 4-0 | 36-21-11 | D04004J | | 31 | | | TB0304Y | C034 | BJ | | 280-299 |
| 276R | 24 | PL | AO | 0-0 | 36-21-11 | D04004J | | 30 | | | TB0304Y | A034 | BJ | | 050-099, 275-278 |
| 276R | 24 | PL | DJ | 0-0 | 36-21-11 | TB0304Y | | | A034 | BJ | D04004J | | 30 | | 150-155, 157, 163-165, 167-199 |
| 276R | 24 | PL | LA | 0-0 | 36-21-11 | TB0304Y | | | A034 | BJ | D04004J | | 30 | | 156, 162, 166 |
| 276R | 24 | PL | LA | 0-0 | 36-21-11 | D04004J | | 30 | | | TB0304Y | A034 | BJ | | 280-299 |
| 277B | 24 | PW | DF | 5-0 | 77-12-11 | D06584J | | 23 | | | TB0304Y | C023 | BJ | | 050-099 |
| 277B | 24 | PW | DF | 6-0 | 77-12-11 | TB0304Y | | | C023 | BJ | D06584J | | 23 | | 150-199, 275-299 |
| 277R | 24 | PW | DF | 0-0 | 77-12-11 | D06584J | | 22 | | | TB0304Y | A023 | BJ | | 050-099 |
| 277R | 24 | PW | DF | 0-0 | 77-12-11 | TB0304Y | | | A023 | BJ | D06584J | | 22 | | 150-199, 275-299 |
| 277Z | | | DF | 0-0 | 77-12-11 | D06584J | | 24 | | | TB0304Y | A024 | BJ | | ALL |
| 278B | 24 | PW | DG | 3-0 | 77-12-11 | D05374J | | 41 | | | TB0304Y | CAP | Y | | 050-099, 150-155, 162-165, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 24

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 278B | 24 | PW | DG | 6-0 | 77-12-11 | D05374J | 41 | | | | TB0304Y | CAP | Y | | 156-157, 166-199, 280-299 |
| 278R | 24 | PW | DG | 0-0 | 77-12-11 | D05374J | 44 | | | | TB0304Y | CAP | Y | | 050-099 |
| 278R | 24 | PW | DG | 0-0 | 77-12-11 | D05374J | 40 | | | | TB0304Y | CAP | Y | | 150-157, 275-276 |
| 278R | 24 | PW | DG | 0-0 | 77-12-11 | D05374J | 44 | | | | TB0304Y | CAP | Y | | 162-199, 277-299 |
| 278Z | | | DG | 0-0 | 77-12-11 | D05374J | 52 | | | | TB0304Y | DED | | | ALL |
| 279B | 24 | PW | LD | 3-0 | 77-35-11 | D05328J | 25 | | | | D04346J | 46 | | | 050-099 |
| 279B | 24 | PW | CI | 5-0 | 77-35-11 | D05328J | 25 | | | | D04346J | 46 | | | 150-199, 275-299 |
| 279R | 24 | PW | LD | 0-0 | 77-35-11 | D05328J | 24 | | | | D04346J | 14 | | | 050-099 |
| 279R | 24 | PW | CI | 0-0 | 77-35-11 | D05328J | 24 | | | | D04346J | 14 | | | 150-199, 275-299 |
| 279Z | | | LD | 0-0 | 77-35-11 | D05328J | 36 | | | | D04346J | 51 | | | 050-099 |
| 279Z | | | CI | 0-0 | 77-35-11 | D05328J | 36 | | | | D04346J | 51 | | | 150-199, 275-299 |
| 280B | 24 | PW | LE | 3-0 | 77-35-11 | D05328J | 23 | | | | D04346J | 23 | | | 050-099 |
| 280B | 24 | PW | BZ | 5-0 | 77-35-11 | D05328J | 23 | | | | D04346J | 23 | | | 150-199, 275-299 |
| 280R | 24 | PW | LE | 0-0 | 77-35-11 | D05328J | 22 | | | | D04346J | 10 | | | 050-099 |
| 280R | 24 | PW | BZ | 0-0 | 77-35-11 | D05328J | 22 | | | | D04346J | 10 | | | 150-199, 275-299 |
| 280Z | | | LE | 0-0 | 77-35-11 | D05328J | 37 | | | | D04346J | 50 | | | 050-099 |
| 280Z | | | BZ | 0-0 | 77-35-11 | D05328J | 37 | | | | D04346J | 50 | | | 150-199, 275-299 |
| 281B | 24 | PW | LF | 4-0 | 73-21-14 | D05328J | 20 | | | | TB0304Z | 21 | BJ | | 050-099 |
| 281B | 24 | PW | BY | 4-0 | 73-21-14 | D05328J | 20 | | | | TB0304Z | 21 | BJ | | 150-199, 275-299 |
| 281R | 24 | PW | LF | 0-0 | 73-21-14 | D05328J | 21 | | | | TB0304Z | 22 | BJ | | 050-099 |
| 281R | 24 | PW | BY | 0-0 | 73-21-14 | D05328J | 21 | | | | TB0304Z | 22 | BJ | | 150-199, 275-299 |
| 281Z | | | LF | 0-0 | 73-21-14 | D05328J | 18 | | | | TB0304Y | A019 | BJ | | 050-099 |
| 281Z | | | BY | 0-0 | 73-21-14 | D05328J | 18 | | | | TB0304Y | A019 | BJ | | 150-199, 275-299 |
| 282B | 24 | PW | NA | 3-0 | 28-41-11 | D05328J | 19 | | | | D04346J | 43 | | | 050-099 |
| 282B | 24 | PW | DM | 5-0 | 28-41-11 | D05328J | 19 | | | | D04346J | 43 | | | 150-199, 275-299 |
| 282R | 24 | PW | NA | 0-0 | 28-41-11 | D05328J | 26 | | | | D04346J | 42 | | | 050-099 |
| 282R | 24 | PW | DM | 0-0 | 28-41-11 | D05328J | 26 | | | | D04346J | 42 | | | 150-199, 275-299 |
| 282Z | | | NA | 0-0 | 28-41-11 | D05328J | 15 | | | | D04346J | 44 | | | 050-099 |
| 282Z | | | DM | 0-0 | 28-41-11 | D05328J | 15 | | | | D04346J | 44 | | | 150-199, 275-299 |
| 283B | 24 | PW | MD | 4-0 | 73-21-17 | D05612J | 27 | | | | D06584J | 13 | | | 050-099 |
| 283B | 24 | PW | MD | 6-0 | 73-21-17 | D05612J | 27 | | | | D06584J | 13 | | | 150-199, 275-299 |
| 283R | 24 | PW | MD | 0-0 | 73-21-12 | D05612J | 16 | | | | D06584J | 14 | | | ALL |
| 283Z | | | MD | 0-0 | 73-21-12 | D05612J | 29 | | | | D06584J | 15 | | | ALL |
| 284B | 24 | PW | LI | 3-0 | 73-21-14 | D05437J | 30 | | | | D06584J | 4 | | | 050-099 |
| 284B | 24 | PW | CN | 6-0 | 73-21-14 | D05437J | 30 | | | | D06584J | 4 | | | 150-199, 275-299 |
| 284R | 24 | PW | LI | 0-0 | 73-21-14 | D05437J | 29 | | | | D06584J | 3 | | | 050-099 |
| 284R | 24 | PW | CN | 0-0 | 73-21-14 | D05437J | 29 | | | | D06584J | 3 | | | 150-199, 275-299 |
| 284Z | | | LI | 0-0 | 73-21-14 | D05437J | 31 | | | | D06584J | | | FW | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 25

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | |
| 284Z | | | | CN | 0-0 | 73-21-14 | D05437J | | 31 | | | | | D06584J | | FW | 150-199, 275-299 |
| 285 | 22 | PA | | | 8-0 | 30-21-11 | D10158 | | C1 | | | | | D05326J | 20 | | 050-099 |
| 285 | 22 | PA | | | 10-0 | 30-21-11 | D10158 | | C1 | | | | | D05326J | 20 | | 150-154 |
| 285 | 22 | PA | | | 9-0 | 30-21-11 | D10158 | | C1 | | | | | D05326J | 20 | | 155-199 |
| 285 | 22 | PA | | | 9-0 | 30-21-11 | D11828 | | A3 | | | | | D05326J | 20 | | 275-299 |
| 286 | 22 | PA | | | 10-0 | 30-21-11 | D11828 | | B1 | | | | | TB0254Y | A004 | BJ | ALL |
| 287 | 20 | PA | | | 6-0 | 30-21-11 | D11828 | | B2 | | | | | GDX0011 | D.. | F | * 050-099, 155-199, 276-299 |
| 287 | 20 | PA | | | 6-0 | 30-21-11 | D11828 | | B2 | | | | | GDX0011 | D.. | F | 150-154, 275 |
| 288 | 22 | PA | | | 10-0 | 30-21-11 | TB0254D | | C011 | 2 | | | | D11828 | X1 | | 050-099 |
| 288 | 22 | PA | | | 10-0 | 30-21-11 | D11828 | | X1 | | | | | TB0254D | C011 | 2 | 150-199, 275-299 |
| 289 | 22 | PA | | | 7-0 | 30-21-11 | TB0254Y | | A004 | BJ | | | | D05326J | 8 | | 050-099 |
| 289 | 22 | PA | | | 6-0 | 30-21-11 | TB0254Y | | A004 | BJ | | | | D05326J | 8 | | 150-199, 275-299 |
| 28A | 24 | PK | | | 8-0 | 21-26-11 | D03788 | | B2 | | | | | D05768J | 60 | | 156-157, 166-199, 277-299 |
| 290 | 22 | PA | | | 10-0 | 30-21-11 | D11828 | | X2 | | | | | TB0254Y | A004 | BJ | ALL |
| 291 | 24 | PK | | | 8-0 | 30-21-11 | D05374J | | 45 | | | | | TB0254Y | A004 | BJ | 050-099, 150-199 |
| 291 | 24 | PK | | | 9-0 | 30-21-11 | D05374J | | 45 | | | | | TB0254Y | A004 | BJ | 275-299 |
| 292B | 24 | PW | LQ | | 6-0 | 32-42-11 | D05768J | | 47 | | | | | TB0274Y | C039 | BJ | 050-099 |
| 292B | 24 | PW | LQ | | 6-0 | 32-42-11 | TB0274Y | | C039 | BJ | | | | D05768J | 47 | | 150-199, 275-299 |
| 292R | 24 | PW | LQ | | 0-0 | 32-42-11 | D05768J | | 46 | | | | | TB0274Y | A039 | BJ | 050-099 |
| 292R | 24 | PW | LQ | | 0-0 | 32-42-11 | TB0274Y | | A039 | BJ | | | | D05768J | 46 | | 150-199, 275-299 |
| 292Z | | | LQ | | 0-0 | 32-42-11 | D05768J | | 48 | | | | | TB0274Y | A040 | BJ | 050-099 |
| 292Z | | | LQ | | 0-0 | 32-42-11 | TB0274Y | | A040 | BJ | | | | D05768J | 48 | | 150-199, 275-299 |
| 299B | 24 | PW | DH | | 4-0 | 77-12-11 | D06260J | | 15 | | | | | TB0304Y | C023 | BJ | ALL |
| 299R | 24 | PW | DH | | 0-0 | 77-12-11 | D06260J | | 28 | | | | | TB0304Y | A023 | BJ | ALL |
| 299Z | | | DH | | 0-0 | 77-12-11 | D06260J | | 32 | | | | | TB0304Y | A024 | BJ | ALL |
| 29A | 24 | PK | | | 8-0 | 21-26-11 | D03788 | | B3 | | | | | D05768J | 61 | | 156-157, 166-199, 277-299 |
| 305B | 24 | PM | V | | 3-0 | 27-81-21 | D05316J | | 14 | | | | | D04962J | 38 | | ALL |
| 305R | 24 | PM | V | | 0-0 | 27-81-21 | D05316J | | 15 | | | | | D04962J | 37 | | ALL |
| 305Y | 24 | PM | V | | 0-0 | 27-81-21 | D05316J | | 16 | | | | | D04962J | 39 | | ALL |
| 307B | 24 | PX | N | | 3-0 | 36-23-21 | D05768J | | 31 | | | | | D04346J | 30 | | ALL |
| 307R | 24 | PX | N | | 0-0 | 36-23-21 | D05768J | | 32 | | | | | D04346J | 31 | | ALL |
| 307Y | 24 | PX | N | | 0-0 | 36-23-21 | D05768J | | 33 | | | | | D04346J | 32 | | ALL |
| 307Z | | | N | | 0-0 | 36-23-21 | D05768J | | 30 | | | | | D04346J | 29 | | ALL |
| 309B | 24 | PX | MI | | 4-0 | 73-31-11 | D05326J | | 24 | | | | | D05328J | 30 | | 050-099 |
| 309B | 24 | PX | BX | | 6-0 | 73-31-11 | D05326J | | 24 | | | | | D05328J | 30 | | 150-199, 275-299 |
| 309R | 24 | PX | MI | | 0-0 | 73-31-11 | D05326J | | 25 | | | | | D05328J | 31 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 26

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 309R | 24 | PX | BX | 0-0 | 73-31-11 | D05326J | | 25 | | | | | D05328J | 31 | | | 150-199, 275-299 |
| 309Y | 24 | PX | MI | 0-0 | 73-31-11 | D05326J | | 26 | | | | | D05328J | 32 | | | 050-099 |
| 309Y | 24 | PX | BX | 0-0 | 73-31-11 | D05326J | | 26 | | | | | D05328J | 32 | | | 150-199, 275-299 |
| 309Z | | | MI | 0-0 | 73-31-11 | D05326J | | 44 | | | | | D05328J | 29 | | | 050-099 |
| 309Z | | | BX | 0-0 | 73-31-11 | D05326J | | 44 | | | | | D05328J | 29 | | | 150-199, 275-299 |
| 310B | 24 | PM | CB | 4-0 | 79-31-11 | D05326J | | 34 | | | | | D05374J | 31 | | | ALL |
| 310R | 24 | PM | CB | 0-0 | 79-31-11 | D05326J | | 33 | | | | | D05374J | 30 | | | ALL |
| 310Y | 24 | PM | CB | 0-0 | 79-31-11 | D05326J | | 32 | | | | | D05374J | 32 | | | ALL |
| 31G | 22 | PA | | 5-0 | 21-66-41 | TB0264D | | A004 | 2 | | | | D05352J | 53 | | | 150, 152-157 |
| 32E | 24 | PK | | 10-0 | 21-45-21 | D05506J | | 2 | | | | | D21192 | X1 | | | 275-299 |
| 32F | 24 | PK | | 10-0 | 21-45-21 | D05506J | | 40 | | | | | D21192 | X2 | | | 275-299 |
| 345 | 24 | PK | | 6-0 | 24-11-21 | TB0304R | | C032 | 2 | | | | D05374J | 35 | | | 050 |
| 345 | 24 | PK | | 6-0 | 24-11-21 | D05374J | | 35 | | | | | TB0304R | C032 | 2 | | 150, 152-199 |
| 345 | 24 | PK | | 6-0 | 24-11-21 | D05374J | | 35 | | | | | TB0304R | C032 | 2 | * | 151 |
| 346 | 24 | PK | | 10-0 | 24-11-21 | TB0304R | | A032 | 2 | | | | D04346J | 39 | | | 050, 150, 152-199 |
| 346 | 24 | PK | | 10-0 | 24-11-21 | TB0304R | | A032 | 2 | * | | | D04346J | 39 | | | 151 |
| 347B | 18 | PC | NV | 10-0 | 21-45-21 | D21192 | | C2 | | | | | C01195 | C2 | D | | 275-299 |
| 347R | 18 | PC | NV | 0-0 | 21-45-21 | D21192 | | A2 | | | | | C01195 | A2 | D | | 275-299 |
| 347Y | 18 | PC | NV | 0-0 | 21-45-21 | D21192 | | B2 | | | | | C01195 | B2 | D | | 275-299 |
| 348B | 18 | PC | NW | 10-0 | 21-45-21 | D05660J | | 14 | | | | | D21192 | C1 | | | 275-299 |
| 348R | 18 | PC | NW | 0-0 | 21-45-21 | D05660J | | 12 | | | | | D21192 | A1 | | | 275-299 |
| 348Y | 18 | PC | NW | 0-0 | 21-45-21 | D05660J | | 13 | | | | | D21192 | B1 | | | 275-299 |
| 401B | 24 | PN | K | 4-0 | 27-51-41 | D05316J | | 19 | | | | | TB0304X | D005 | BJ | | ALL |
| 401G | 24 | PN | K | 0-0 | 27-51-41 | D05316J | | 20 | | | | | TB0304X | A005 | BJ | | ALL |
| 401R | 24 | PN | K | 0-0 | 27-51-41 | D05316J | | 21 | | | | | TB0304X | C005 | BJ | | ALL |
| 401Y | 24 | PN | K | 0-0 | 27-51-41 | D05316J | | 22 | | | | | TB0304X | B005 | BJ | | ALL |
| 501 | 24 | PK | | 7-0 | 21-58-16 | D10892 | | X1 | | | | | TB0192Z | 16 | BJ | | 050-099, 155-199, 276-299 |
| 501 | 24 | PK | | 7-0 | 21-58-16 | D10892 | | X1 | | | | | TB0192Y | C007 | BJ | | 150-154, 275 |
| 502 | 24 | PK | | 5-0 | 21-58-15 | D05612J | | 20 | | | | | TB0212Y | A012 | BJ | | ALL |
| 504 | 24 | PK | | 5-0 | 21-58-15 | K00345 | | X2 | C | | | | D06076J | 2 | | | ALL |
| 505 | 24 | PK | | 7-0 | 32-09-12 | D03728 | | A2 | | | | | TB0082Z | 7 | BJ | | ALL |
| 506 | 20 | PA | | 3-0 | 27-81-21 | D10014 | | A2 | | | | | D02918 | A3 | | | ALL |
| 507 | 22 | PA | | 9-0 | 29-11-12 | D05612J | | 23 | | | | | TB0082Y | A005 | BJ | | 050-099 |
| 507 | 22 | PA | | 8-0 | 29-11-12 | D05612J | | 23 | | | | | TB0082Y | A005 | BJ | | 150-199, 275-299 |
| 508 | 24 | PK | | 3-0 | 21-51-21 | D04004J | | 9 | | | | | D06260J | 12 | | | ALL |
| 509 | 24 | PK | | 6-0 | 24-22-21 | TB0190Y | | C010 | BJ | | | | D05768J | 22 | | | ALL |
| 50F | 22 | PA | | 7-0 | 49-61-11 | D10582 | | 12 | | | | | TB0212X | B002 | BJ | | 050-099 |
| 50F | 22 | PA | | 8-0 | 49-61-11 | TB0212X | | B002 | BJ | | | | D10582 | 12 | | | 162-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 27

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 50G | 22 | | PA | | 7-0 | 49-61-11 | D10582 | | | | TB0212Z | 20 | BJ | | 050-099 |
| 50G | 22 | | PA | | 8-0 | 49-61-11 | TB0212Z | 20 | BJ | | D10582 | 6 | | | 162-199 |
| 50G | 22 | | PA | | 7-0 | 49-61-11 | TB0212Z | 20 | BJ | | D10582 | 6 | | | 275-299 |
| 50K | 20 | | PA | | 12-0 | 49-61-11 | D10582 | 11 | | | GDX0003 | D.. | 2 | | 050-099, 162-199 |
| 50K | 20 | | PA | | 8-0 | 49-61-11 | D10582 | 11 | | | GDX0003 | D.. | 2 | | 275-299 |
| 50L | 20 | | PA | | 12-0 | 49-61-11 | D10582 | 7 | | | GDX0003 | D.. | 2 | | 050-099, 162-199 |
| 50L | 20 | | PA | | 10-0 | 49-61-11 | D10582 | 7 | | | GDX0003 | D.. | 2 | | 275-299 |
| 50M | 24 | | PK | | 10-0 | 49-72-11 | D05328J | 41 | | | D10582 | 10 | | | 050-099 |
| 50M | 24 | | PK | | 11-0 | 49-72-11 | D10582 | 10 | | | D05328J | 41 | | | 162-199 |
| 50M | 24 | | PK | | 10-0 | 49-72-11 | D10582 | 10 | | | D05328J | 41 | | | 275-299 |
| 50P | 18 | | PA | | 12-0 | 23-32-41 | D05561J | 6 | DK | | TB0084F | C005 | 2 | | 275-299 |
| 50R | 18 | | PA | | 12-0 | 23-32-51 | D05561J | 7 | DK | | TB0084F | A006 | 2 | | 275-299 |
| 50U | 18 | | PA | | 12-0 | 23-32-61 | D05561J | 8 | DK | | TB0084F | C006 | 2 | | 275-299 |
| 50X | 18 | | PA | | 12-0 | 23-32-31 | D05561J | 5 | DK | | TB0084F | A005 | 2 | | 275-299 |
| 511 | 24 | | PV | AK | 6-0 | 21-58-11 | D06260J | 14 | | | TB0212Y | C008 | BJ | | ALL |
| 511Z | | | | AK | 0-0 | 21-58-11 | D06260J | | DED | | TB0212Y | DED | | | ALL |
| 512 | 24 | | PK | | 4-0 | 21-61-11 | D05612J | 38 | | | D03678 | X1 | | | ALL |
| 512R | 22 | | PH | | 4-0 | 26-17-11 | TB0304X | D006 | BJ | | D05068J | 23 | | | ALL |
| 513 | 22 | | PA | | 9-0 | 22-14-31 | D05437J | 1 | | | TB0084Y | A007 | BJ | | ALL |
| 514 | 22 | | PA | | 9-0 | 22-14-31 | D05437J | 2 | | | TB0084Y | C007 | BJ | | ALL |
| 515 | 20 | | PA | | 7-0 | 25-33-11 | D05266J | 23 | | | TB0254Y | A006 | BJ | | 050-099, 162-164, 277-299 |
| 515 | 20 | | PA | | 8-0 | 25-33-11 | D05266J | 23 | | | TB0254Y | A006 | BJ | | 155-157, 165-199 |
| 516 | 24 | | PK | | 2-0 | 21-58-16 | TB0088D | C013 | 2 | | TB0088D | C003 | 2 | | 050-099 |
| 516 | 24 | | PK | | 4-0 | 21-58-16 | D10892 | X2 | | | TB0088D | A003 | 2 | | 150-152, 275-276 |
| 516 | 24 | | PK | | 4-0 | 21-58-16 | TB0088D | C013 | 2 | | TB0088D | C003 | 2 | | 153-154 |
| 516 | 24 | | PK | | 1-0 | 21-58-16 | TB0088D | C013 | 2 | | TB0088D | C003 | 2 | | 155-199, 277-299 |
| 517 | 24 | | PK | | 7-0 | 32-09-12 | D02270 | 6 | | | TB0084Z | 10 | BJ | | ALL |
| 518 | 24 | | PK | | 3-0 | 32-09-12 | D02270 | 12 | | | TB0082Y | A006 | BJ | | ALL |
| 519 | 20 | | PA | | 3-0 | 27-32-21 | D02270 | 1 | | | GDX0014 | D.. | 2 | | ALL |
| 51B | 24 | | PK | | 6-0 | 78-36-21 | D05352J | 53 | | | TB0274Y | CAP | Y | | 050-099, 151, 162-166, 275-276 |
| 51B | 24 | | PK | | 6-0 | SPARE | D05352J | 53 | | | TB0274Y | CAP | Y | | 167-199, 277-299 |
| 51C | 24 | | PK | | 6-0 | 78-36-21 | D05352J | 55 | | | TB0274Y | CAP | Y | | 050-099, 150-156, 162-166, 275-276 |
| 51C | 24 | | PK | | 6-0 | SPARE | D05352J | 55 | | | TB0274Y | CAP | Y | | 157, 167-199, 277-299 |
| 51F | 24 | | PK | | 6-0 | 78-36-21 | D05352J | 54 | | | TB0274Y | CAP | Y | | 050-099, 150-156, 162-166, 275-276 |
| 51F | 24 | | PK | | 6-0 | SPARE | D05352J | 54 | | | TB0274Y | CAP | Y | | 157, 167-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 28

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | |
| 51H | 20 | | PA | 8-0 | 38-32-11 | TB0210X | D020 | BJ | | D05437J | 12 | | | 050-099, 155-199, 277-299 | | |
| 51H | 20 | | PA | 8-0 | SPARE | TB0210X | D020 | BJ | | D05437J | 12 | | | 276 | | |
| 522 | 24 | | PK | 8-0 | 21-58-16 | TB0088D | C013 | 2 | | TB0210X | C019 | BJ | | 050-099, 153-199, 277-299 | | |
| 522 | 24 | | PK | 8-0 | 21-58-16 | TB0088D | C003 | 2 | | TB0210X | C019 | BJ | | 150-152, 275-276 | | |
| 523 | 24 | | PK | 8-0 | 21-58-16 | TB0088D | C003 | 2 | | TB0210X | B019 | BJ | | ALL | | |
| 524 | 22 | | PA | 8-0 | 25-33-11 | TB0088D | C005 | 2 | | D05352J | 52 | | | 050-099 | | |
| 524 | 22 | | PA | 8-0 | 25-33-11 | D05352J | | 52 | | TB0088D | C005 | 2 | | 150-199, 277-299 | | |
| 524 | 22 | | PA | 8-0 | 21-58-16 | D05352J | | 52 | | TB0088D | C005 | 2 | | 275-276 | | |
| 525 | 24 | | PK | 9-0 | 34-31-31 | D05437J | | 15 | | D03698 | 10 | | | ALL | | |
| 526 | 24 | | PK | 15-0 | 36-21-11 | TB0190Y | C005 | BJ | | D04284J | 26 | | | 050-099, 150-155, 162-165, 275-276 | | |
| 526 | 24 | | PK | 5-0 | 36-21-11 | TB0320Y | C009 | BJ | | D04284J | 26 | | | 156-157, 166-199, 277-299 | | |
| 527 | 22 | | PA | 6-0 | 21-61-11 | D05612J | | 39 | | TB0192Y | A012 | BJ | | ALL | | |
| 528 | 24 | | PK | 4-0 | 21-61-11 | D05612J | | 40 | | D03678 | C2 | | | ALL | | |
| 529 | 24 | | PK | 9-0 | 31-31-11 | D03714 | | D3 | | D05435J | 2 | | | ALL | | |
| 530 | 24 | | PK | 9-0 | 31-31-11 | D03714 | | D2 | | D05435J | 1 | | | ALL | | |
| 531R | 22 | | PH | 4-0 | 26-18-21 | D05068J | | 4 | | TB0304X | D004 | BJ | | ALL | | |
| 533 | 24 | | PK | 3-0 | 38-15-11 | D04284J | | 20 | | D05688J | 15 | | | ALL | | |
| 535 | 24 | | PK | 4-0 | 21-61-11 | D05612J | | 41 | | D03678 | B3 | | | ALL | | |
| 536 | 24 | | PK | 4-0 | 21-61-11 | D05612J | | 42 | | D03678 | C3 | | | ALL | | |
| 537 | 24 | | PK | 4-0 | 21-61-11 | D05612J | | 43 | | D03678 | D3 | | | ALL | | |
| 538 | 24 | | PK | 4-0 | 21-61-11 | D05612J | | 44 | | D03678 | X2 | | | ALL | | |
| 540 | 20 | | PA | 3-0 | 27-23-11 | D06260J | | 7 | | D05318J | 2 | | | ALL | | |
| 541 | 20 | | PA | 3-0 | 27-23-11 | D05316J | | 33 | | D05318J | 1 | | | ALL | | |
| 542 | 22 | | PA | 4-0 | 27-23-11 | D06260J | | 5 | | TB0304Y | A015 | BJ | | ALL | | |
| 545 | 24 | | PK | 7-0 | 21-58-16 | D06076J | | 8 | | D10074 | 8 | | | ALL | | |
| 546 | 22 | | PQ | 7-0 | 29-11-12 | D05352J | | 21 | | TB0212Y | C010 | BJ | | ALL | | |
| 546Z | | | BO | 0-0 | 29-11-12 | D05352J | DED | | | TB0212Y | DED | | | ALL | | |
| 547 | 22 | | PA | 6-0 | 78-34-21 | D03670 | | B1 | | D20104 | B3 | | | 050-099, 150-156, 162-199, 275-278 | | |
| 547 | 22 | | PA | 10-0 | 78-34-21 | D03670 | | B1 | | D20104 | B3 | | | 157, 280-299 | | |
| 548 | 24 | | PK | 3-0 | 78-34-21 | D03670 | | X1 | | TB0084Z | 3 | BJ | | ALL | | |
| 549 | 24 | | PK | 3-0 | 78-34-21 | D03670 | | B2 | | TB0084Z | 3 | BJ | | ALL | | |
| 54V | 20 | | PA | 5-0 | 30-71-24 | TB0210Y | A001 | BJ | | D05688J | 3 | | | 050-099 | | |
| 54X | 20 | | PA | 5-0 | 30-71-24 | TB0210Y | A004 | BJ | | D05688J | 17 | | | 050 | | |
| 54X | 20 | | PA | 4-0 | 30-71-24 | TB0320Y | A011 | BJ | | D05688J | 17 | | | 051-099 | | |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 29

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 550 | 24 | PV | CP | 7-0 | 29-21-31 | D03714 | C1 | | | TB0190Y | A005 | BJ | | ALL | |
| 550Z | | | CP | 0-0 | 29-21-31 | D03714 | DED | | | TB0190Y | DED | | | ALL | |
| 551 | 24 | PV | CQ | 7-0 | 29-21-31 | D03714 | C2 | | | TB0190X | B003 | BJ | | ALL | |
| 551Z | | | CQ | 0-0 | 29-21-31 | D03714 | DED | | | TB0190X | DED | | | ALL | |
| 552 | 24 | PV | CR | 7-0 | 29-21-31 | D03714 | C3 | | | TB0190X | C003 | BJ | | ALL | |
| 552Z | | | CR | 0-0 | 29-21-31 | D03714 | DED | | | TB0190X | DED | | | ALL | |
| 553 | 18 | PA | | 10-0 | 27-81-11 | D05316J | 31 | DL | | TB0084G | 12 | 2 | | ALL | |
| 554 | 22 | PA | | 10-0 | 27-81-21 | D05328J | 4 | | | K00223 | X1 | C | | ALL | |
| 555 | 22 | PA | | 9-0 | 27-81-21 | D05316J | 35 | | | K00222 | X2 | C | | ALL | |
| 556 | 22 | PA | | 9-0 | 27-81-21 | D05316J | 36 | | | K00221 | X2 | C | | ALL | |
| 557 | 18 | PA | | 7-0 | 27-81-11 | D05326J | 39 | DL | | TB0190G | 1 | 2 | | ALL | |
| 558 | 22 | PA | | 9-0 | 27-81-11 | D05326J | 40 | | | TB0082G | 11 | 2 | | ALL | |
| 559 | 22 | PA | | 8-0 | 27-81-11 | D05316J | 37 | | | D01926 | X2 | | | ALL | |
| 560 | 22 | PA | | 8-0 | 27-81-11 | D05316J | 44 | | | TB0254Y | A002 | BJ | | ALL | |
| 561 | 18 | PA | | 7-0 | 27-81-11 | D05316J | 43 | DL | | TB0190G | 1 | 2 | | ALL | |
| 562 | 22 | PA | | 9-0 | 27-81-11 | D05316J | 42 | | | D10012 | A1 | | | ALL | |
| 563 | 18 | PA | | 6-0 | 27-81-11 | D01926 | A1 | | | TB0190G | 1 | 2 | | ALL | |
| 564 | 18 | PA | | 3-0 | 27-81-11 | D01926 | A2 | | | TB0084G | 12 | 2 | | ALL | |
| 565 | 22 | PA | | 3-0 | 27-81-11 | D01926 | X1 | | | TB0084G | 12 | 2 | | ALL | |
| 566 | 24 | PK | | 4-0 | 21-61-11 | D05612J | 45 | | | D03678 | D2 | | | ALL | |
| 567 | 24 | PK | | 8-0 | 21-61-21 | D05612J | 46 | | | D03716 | X1 | | | ALL | |
| 568 | 24 | PK | | 5-0 | 21-61-21 | D05612J | 47 | | | TB0320Y | C033 | BJ | | 050-099 | |
| 568 | 24 | PK | | 7-0 | 21-61-21 | D05612J | 47 | | | TB0210Y | A001 | BJ | | 150-199 | |
| 568 | 24 | PK | | 6-0 | 21-61-21 | D05612J | 47 | | | TB0210Y | A001 | BJ | | 275-278 | |
| 568 | 24 | PK | | 6-0 | 21-61-21 | D05612J | 47 | | | TB0320Y | C033 | BJ | | 280-299 | |
| 569 | 18 | PA | | 10-0 | 27-81-21 | TB0084G | 11 | 2 | | D05316J | 38 | DL | | ALL | |
| 570 | 22 | PA | | 7-0 | 27-81-11 | TB0190F | C008 | 2 | | D05326J | 38 | | | ALL | |
| 571 | 22 | PA | | 7-0 | 27-81-11 | TB0190X | A004 | BJ | | D05316J | 9 | | | ALL | |
| 572 | 22 | PA | | 7-0 | 27-81-11 | TB0190X | B004 | BJ | | D05316J | 10 | | | ALL | |
| 573 | 18 | PA | | 6-0 | 27-81-21 | TB0274G | 8 | 2 | | D05328J | 5 | DL | | ALL | |
| 574 | 20 | PA | | 9-0 | 27-81-21 | TB0082G | 10 | 2 | | D05328J | 6 | | | ALL | |
| 575 | 22 | PA | | 8-0 | 27-81-21 | D02918 | X2 | | | D05316J | 11 | | | ALL | |
| 576 | 18 | PA | | 3-0 | 27-81-21 | D02918 | A2 | | | TB0084G | 11 | 2 | | ALL | |
| 577 | 22 | PA | | 3-0 | 27-81-21 | D02918 | X1 | | | TB0084G | 11 | 2 | | ALL | |
| 578 | 18 | PA | | 6-0 | 27-81-21 | D02918 | A1 | | | TB0274G | 8 | 2 | | ALL | |
| 579 | 20 | PA | | 8-0 | 27-81-21 | D10014 | A1 | | | D04962J | 32 | | | ALL | |
| 583 | 24 | PK | | 7-0 | 34-55-21 | D05435J | 37 | | | D03700 | 9 | | | ALL | |
| 584 | 20 | PA | | 3-0 | 34-55-21 | GDX0014 | D.. | 2 | | D03700 | 11 | | | ALL | |
| 585 | 24 | PK | | 7-0 | 32-09-12 | D00640 | 6 | | | TB0084Z | 13 | BJ | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W0190
Page 30
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 586 | 24 | | PK | | 3-0 | 32-09-12 | D00640 | | 12 | | | | TB0082Z | 8 | BJ | | ALL |
| 587 | 24 | | PK | | 9-0 | 32-09-12 | D04646J | | 12 | | | | TB0084Y | C002 | BJ | | ALL |
| 588 | 24 | | PK | | 7-0 | 21-58-16 | D10892 | | A3 | | | | TB0192Z | 16 | BJ | | 050-099, 155-199, 276-299 |
| 588 | 24 | | PK | | 7-0 | 21-58-16 | D10892 | | A3 | | | | TB0192Y | C007 | BJ | | 150-154, 275 |
| 591 | 24 | | PK | | 3-0 | 32-09-12 | D02904 | | 6 | | | | TB0084Z | 10 | BJ | | ALL |
| 592 | 24 | | PK | | 11-0 | 32-09-12 | M01163 | | B | C | | | D05316J | 57 | | | ALL |
| 596 | 22 | | PA | | 3-0 | 27-09-12 | D05317J | | 3 | | | | D06260J | 3 | | | ALL |
| 597 | 22 | | PA | | 7-0 | 74-31-21 | D05328J | | 1 | | | | D10158 | D1 | | * | 050-099 |
| 597 | 22 | | PA | | 12-0 | 74-31-21 | D05328J | | 1 | | | | D10158 | D1 | | * | 150-199, 275-299 |
| 598 | 22 | | PA | | 10-0 | 27-09-12 | D05319J | | 3 | | | | D03698 | 5 | | | ALL |
| 599 | 22 | | PQ | DA | 7-0 | 74-31-21 | D05326J | | 3 | | | | D10158 | B1 | | * | ALL |
| 599Z | | | | DA | 0-0 | 74-31-21 | D05326J | | DED | | | | D10158 | DED | | | ALL |
| 59M | 20 | | PA | | 4-0 | 29-11-12 | GDX0018 | | D.. | E | | | GDX0011 | D.. | F | | 050-099, 155-199 |
| 59M | 20 | | PA | | 4-0 | 29-11-12 | GDX0018 | | D.. | E | | | GDX0010 | D.. | P | | 150-154 |
| 59M | 20 | | PA | | 5-0 | 29-11-12 | GDX0018 | | D.. | E | | | GDX0010 | D.. | F | | 275 |
| 59M | 20 | | PA | | 5-0 | 29-11-12 | GDX0018 | | D.. | E | | | GDX0011 | D.. | F | | 276-299 |
| 59N | 20 | | PA | | 5-0 | 30-71-24 | TB0210Y | | A004 | BJ | | | D05688J | 18 | | | 050 |
| 59N | 20 | | PA | | 4-0 | 30-71-24 | TB0320Y | | A011 | BJ | | | D05688J | 18 | | | 051-099 |
| 59W | 24 | | PK | | 8-0 | 24-27-41 | D10582 | | 8 | | | | TB0274X | D013 | BJ | | 050-099 |
| 59W | 24 | | PK | | 9-0 | 24-27-41 | D10582 | | 8 | | | | TB0274X | D013 | BJ | | 162-199, 275-299 |
| 5A1 | 24 | | PK | | 12-0 | 27-89-11 | D04934J | | 27 | | | | D21190 | X1 | | | 050-099, 151 |
| 5A1 | 24 | | PK | | 12-0 | 27-89-11 | D04934J | | CAP | Y | | | D21190 | X1 | | | 150, 152-199, 275-299 |
| 5A4 | 24 | | PK | | 12-0 | 27-89-11 | D04934J | | 28 | | | | D21190 | A2 | | | ALL |
| 5A5 | 24 | | PK | | 12-0 | 27-89-11 | D04934J | | 29 | | | | D21190 | B2 | | | ALL |
| 5A6 | 24 | | PK | | 12-0 | 27-89-11 | D04934J | | 30 | | | | D21190 | C2 | | | ALL |
| 5A8 | 24 | | PK | | 12-0 | 27-89-11 | D05330J | | 13 | | | | D21190 | X2 | | | 050-099, 162-199 |
| 5A8 | 24 | | PK | | 12-0 | 27-89-11 | D05330J | | 24 | | | | D21190 | X2 | | | 150-157, 275-299 |
| 5A9 | 20 | | PA | | 12-0 | 27-89-11 | D21190 | | A3 | | | | GDX0009 | D.. | 2 | | ALL |
| 5B1 | 20 | | PA | | 12-0 | 27-89-11 | D21190 | | B3 | | | | GDX0009 | D.. | 2 | | ALL |
| 5B2 | 20 | | PA | | 12-0 | 27-89-11 | D21190 | | C3 | | | | GDX0009 | D.. | 2 | | ALL |
| 602 | 24 | | PK | | 7-0 | 27-32-21 | D05437J | | 5 | | | | D02270 | 13 | | | ALL |
| 603 | 24 | | PK | | 9-0 | 73-21-17 | D05316J | | 45 | | | | D03668 | B2 | | | ALL |
| 605 | 20 | | PA | | 2-0 | 73-21-17 | GDX0015 | | D.. | 2 | | | D03668 | B3 | | | ALL |
| 606 | 22 | | PA | | 7-0 | 74-31-21 | D05328J | | 10 | | | | TB0192X | C010 | BJ | | ALL |
| 607 | 22 | | PQ | CX | 7-0 | 74-31-21 | D05326J | | 6 | | | | TB0192X | D010 | BJ | | ALL |
| 607Z | | | | CX | 0-0 | 74-31-21 | D05326J | | DED | | | | TB0192X | DED | | | ALL |
| 608 | 24 | | PK | | 7-0 | 77-35-11 | TB0212Y | | A013 | BJ | | | D00640 | 3 | | | 050-099, 150-199 |
| 608 | 24 | | PK | | 9-0 | 77-35-11 | TB0212Y | | A013 | BJ | | | D00640 | 3 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 31

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 609 | 20 | | PA | | 6-0 | 77-35-11 | GDX0015 | D.. | 2 | | D00640 | | 5 | | ALL |
| 60B | 08 | | PA | | 10-0 | 24-54-21 | TB5132 | | 7 | E | C00665 | | 2 | D | 150-157, 275-276 |
| 60XB | 24 | | PL | W | 4-0 | 36-23-21 | D04346J | | 35 | | D05602J | | 6 | | 050-099 |
| 60XB | 24 | | PL | FQ | 4-0 | 36-23-21 | D04346J | | 35 | | D05602J | | 6 | | 150-157, 163-199, 275-299 |
| 60XB | 24 | | PL | FQ | 6-0 | 36-23-21 | D04346J | | 35 | | D05602J | | 6 | | 162 |
| 60XR | 24 | | PL | W | 0-0 | 36-23-21 | D04346J | | 55 | | D05602J | | 5 | | 050-099 |
| 60XR | 24 | | PL | FQ | 0-0 | 36-23-21 | D04346J | | 55 | | D05602J | | 5 | | 150-199, 275-299 |
| 613 | 20 | | PA | | 5-0 | 33-42-11 | D04284J | | 17 | | TB0274Y | A010 | BJ | | ALL |
| 614 | 20 | | PA | | 5-0 | 33-42-11 | D05266J | | 11 | | TB0274Y | A010 | BJ | | ALL |
| 615 | 20 | | PA | | 6-0 | 33-42-11 | D05266J | | 10 | | TB0192Y | C015 | BJ | | ALL |
| 617 | 24 | | PK | | 7-0 | 36-11-41 | D05352J | | 12 | | TB0274Y | A033 | BJ | | ALL |
| 618 | 24 | | PK | | 6-0 | 36-11-41 | D05352J | | 14 | | D10478 | A1 | | | ALL |
| 619 | 24 | | PK | | 12-0 | 36-11-41 | D05352J | | 13 | | D10582 | | 4 | | 050-099, 162-199, 275-299 |
| 619 | 24 | | PK | | 3-0 | 36-11-41 | D05352J | | 13 | | D05688J | | 6 | | 150-157 |
| 61A | 24 | | PK | | 7-0 | 24-11-21 | D05316J | | 50 | | D11522 | | 8 | | 050-099 |
| 61A | 24 | | PK | | 8-0 | 24-11-21 | D05316J | | 50 | | D11522 | | 8 | | 150-199, 275-299 |
| 61B | 24 | | PK | | 6-0 | 24-11-21 | D04346J | | 38 | | D11522 | | 7 | | 050-099 |
| 61B | 24 | | PK | | 8-0 | 24-11-21 | D04346J | | 38 | | D11522 | | 7 | | 150-199, 275-299 |
| 61C | 24 | | PK | | 6-0 | 24-11-21 | TB0304R | A032 | 2 | | D11522 | | 6 | | 050 |
| 61C | 24 | | PK | | 6-0 | 24-11-21 | D04346J | | 39 | | D11522 | | 6 | | 051-099 |
| 61C | 24 | | PK | | 8-0 | 24-11-21 | TB0304R | A032 | 2 | | D11522 | | 6 | | 150, 152-199 |
| 61C | 24 | | PK | | 8-0 | 24-11-21 | TB0304R | A032 | 2 | * | D11522 | | 6 | | 151 |
| 61C | 24 | | PK | | 8-0 | 24-11-21 | D04346J | | 39 | | D11522 | | 6 | | 275-299 |
| 61D | 20 | | PA | | 2-0 | 24-11-21 | GDX0002 | D.. | 2 | | D11522 | | 3 | | 050-099 |
| 61D | 20 | | UA | | 3-0 | 24-11-21 | D11522 | | 3 | | GDX0002 | D.. | 2 | | 150-199, 275-277 |
| 61D | 20 | | PA | | 3-0 | 24-11-21 | D11522 | | 3 | | GDX0002 | D.. | 2 | | 278-299 |
| 61H | 20 | | PA | | 8-0 | 25-31-12 | D05266J | | 23 | | TB0254G | | 16 | BJ | 150-152 |
| 61H | 20 | | PA | | 8-0 | 25-31-12 | D05266J | | 23 | | TB0254Z | | 16 | BJ | 153-154 |
| 61P | 24 | | PK | | 3-0 | 32-09-12 | TB0084Z | | 13 | BJ | TB0084Y | C002 | BJ | | ALL |
| 61Q | 18 | | PA | | 9-0 | 23-32-31 | D05561J | | 9 | DK | GDX0009 | A.. | 2 | | 277-299 |
| 61R | 18 | | PA | | 9-0 | 23-32-41 | D05561J | | 10 | DK | GDX0009 | A.. | 2 | | 277-299 |
| 61S | 18 | | PA | | 9-0 | 23-32-51 | D05561J | | 11 | DK | GDX0009 | A.. | 2 | | 277-299 |
| 620 | 22 | | PA | | 4-0 | 36-11-41 | D05352J | | 19 | | TB0304Y | C012 | BJ | | ALL |
| 621 | 24 | | PK | | 6-0 | 36-11-41 | TB0274D | A031 | 2 | | D10478 | A2 | | | ALL |
| 622 | 24 | | PK | | 4-0 | 36-11-41 | TB0304X | C004 | BJ | | D05688J | | 8 | | ALL |
| 626 | 12 | | PA | | 6-0 | 21-58-15 | D06288J | | 4 | | K00345 | C1 | E | | ALL |
| 627 | 12 | | PA | | 6-0 | 21-58-15 | D06288J | | 5 | | K00345 | B1 | E | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 32

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|--------|-------------|------|----|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | | | |
| 628 | 12 | | PA | | 6-0 | 21-58-15 | D06288J | | | | 6 | | | | K00345 | A1 | E | | ALL |
| 629 | 24 | | PK | | 8-0 | 21-61-21 | D05612J | | | | 48 | | | | D03716 | C2 | | | ALL |
| 62W | 18 | | PA | | 9-0 | 23-32-61 | D05561J | | | | 12 | DK | | | GDX0009 | A.. | 2 | | 277-299 |
| 630 | 24 | | PK | | 7-0 | 23-31-13 | TB0192X | | | B019 | | BJ | | | D05541J | 3 | | | ALL |
| 636 | 24 | | PK | | 8-0 | 34-53-21 | D03684 | | | | 7 | | | | D05435J | 22 | | | ALL |
| 637 | 20 | | PA | | 2-0 | 34-53-21 | D03684 | | | | 8 | | | | GDX0014 | D.. | 2 | | ALL |
| 638 | 22 | | PA | | 9-0 | 27-09-12 | D04004J | | | | 4 | | | | D03698 | 3 | | | ALL |
| 639 | 20 | | PA | | 2-0 | 31-51-21 | D02904 | | | | 5 | | | | GDX0015 | D.. | 2 | | ALL |
| 63A | 22 | | PQ | EQ | 6-0 | 28-42-13 | D05068J | | | | 43 | | | | D12158 | A1 | | | 050-099, 155-199, 276-299 |
| 63AZ | | | | EQ | 0-0 | 28-42-13 | D05068J | | | DED | | | | | D12158 | DED | | | 050-099, 155-199, 276-299 |
| 63B | 22 | | PQ | ER | 8-0 | 28-42-13 | D12158 | | | | A2 | | | | TB0304Y | A025 | BJ | | 050-099, 155-199, 276-299 |
| 63BZ | | | | ER | 0-0 | 28-42-13 | D12158 | | | DED | | | | | TB0304Y | DED | | | 050-099, 155-199, 276-299 |
| 63C | 22 | | PQ | EO | 10-0 | 28-42-12 | D12158 | | | | B1 | | | | TB0212Z | 19 | BJ | | 050-099, 155-199, 276-299 |
| 63CZ | | | | EO | 0-0 | 28-42-12 | D12158 | | | DED | | | | | TB0212Z | DED | | | 050-099, 155-199, 276-299 |
| 63D | 22 | | PQ | EP | 6-0 | 28-42-12 | D04284J | | | | 15 | | | | D12158 | B2 | | | 050-099, 155-199, 276-299 |
| 63DZ | | | | EP | 0-0 | 28-42-12 | D04284J | | | DED | | | | | D12158 | DED | | | 050-099, 155-199, 276-299 |
| 63E | 24 | | PK | | 10-0 | 28-22-12 | D12158 | | | | C1 | | | | TB0212Z | 17 | BJ | | 050-099, 155-199, 276-299 |
| 63F | 24 | | PK | | 6-0 | 28-22-12 | D04284J | | | | 14 | | | | D12158 | C2 | | | 050-099, 155-199, 276-299 |
| 63G | 24 | | PK | | 7-0 | 28-22-12 | D12158 | | | | D1 | | | | TB0082Y | A003 | BJ | | 050-099, 155-199, 276-299 |
| 63J | 20 | | PA | | 7-0 | 28-22-12 | D12158 | | | | D2 | | | | GDX0004 | D.. | 2 | | 050-099, 155-199, 276-299 |
| 63K | 22 | | PA | | 7-0 | 28-31-21 | D12158 | | | | X1 | | | | TB0082Y | A004 | BJ | | 050-099, 155-199, 276-299 |
| 63L | 20 | | PA | | 7-0 | 28-31-21 | D12158 | | | | X2 | | | | GDX0004 | D.. | 2 | | 050-099, 155-199, 276-299 |
| 63M | 24 | | PK | | 3-0 | 36-11-62 | D10158 | | | CAP | Y | | | | D02001 | X2 | | | 050-099 |
| 63M | 24 | | PK | | 3-0 | 36-11-62 | D02001 | | | | X2 | | | | D10158 | CAP | Y | | 150-156, 162-166, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 33

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 63Q | 24 | | PK | | 4-0 | 21-58-16 | D10892 | | X2 | | TB0088D | A013 | 2 | | 050-099, 153-199, 277-299 |
| 63W | 22 | | PQ | ES | 6-0 | 28-42-13 | D04284J | | 13 | | TB0304Y | A025 | BJ | | 050-099 |
| 63W | 22 | | PQ | ES | 4-0 | 28-42-13 | D04284J | | 13 | | TB0304Y | A025 | BJ | | 155-199, 276-299 |
| 63WZ | | | | ES | 0-0 | 28-42-13 | D04284J | | DED | | TB0304Y | DED | | | 050-099, 155-199, 276-299 |
| 63Y | 22 | | PQ | ET | 3-0 | 28-42-13 | D05374J | | 28 | | TB0304Y | A025 | BJ | | 050-099, 155-199, 276-299 |
| 63YZ | | | | ET | 0-0 | 28-42-13 | D05374J | | DED | | TB0304Y | DED | | | 050-099, 155-199, 276-299 |
| 640 | 24 | | PK | | 9-0 | 31-51-21 | D02904 | | 4 | | D05435J | | 11 | | ALL |
| 641 | 20 | | PA | | 2-0 | 31-51-33 | D02904 | | 7 | | GDX0015 | D.. | 2 | | ALL |
| 642 | 24 | | PK | | 9-0 | 31-51-33 | D02904 | | 8 | | D05435J | | 12 | | ALL |
| 643 | 20 | | PA | | 3-0 | 31-51-41 | D02270 | | 7 | | GDX0004 | D.. | 2 | | ALL |
| 644 | 24 | | PK | | 7-0 | 31-51-41 | D02270 | | 8 | | D05437J | | 3 | | ALL |
| 646 | 24 | | PK | | 8-0 | 21-61-21 | D05612J | | 51 | | D03716 | | D3 | | ALL |
| 647 | 22 | | PA | | 5-0 | 21-61-21 | D05612J | | 52 | | TB0210Z | | 12 | BJ | ALL |
| 648 | 24 | | PK | | 8-0 | 21-61-21 | D05612J | | 53 | | D03716 | | D2 | | ALL |
| 649 | 20 | | PA | | 3-0 | 49-61-11 | D03700 | | 2 | | GDX0014 | D.. | 2 | | ALL |
| 64A | 20 | | PA | | 3-0 | 30-34-21 | D06584J | | 8 | | D05316J | | 25 | | 050-099 |
| 64A | 20 | | PA | | 5-0 | 30-34-21 | D06584J | | 8 | | D05316J | | 25 | | 150-199 |
| 64A | 20 | | PA | | 4-0 | 30-34-21 | D06584J | | 8 | | D05316J | | 25 | | 275-299 |
| 64C | 20 | | PA | | 8-0 | 24-51-72 | K02092 | | X1 | C | TB0088D | C011 | 2 | | 050-099, 162-164, 276 |
| 64D | 20 | | PA | | 6-0 | 24-51-72 | D05290J | | 1 | | K02092 | X2 | C | | 050-099, 162-164, 276 |
| 64D | 20 | | PA | | 7-0 | 24-51-72 | GDX0003 | | D.. | 2 | K02092 | X2 | C | | 155, 165 |
| 64D | 20 | | PA | | 7-0 | 24-51-72 | GDX0004 | | D.. | 2 | K02092 | X2 | C | | 156-157, 166-199, 277-299 |
| 64G | 22 | | PA | | 7-0 | 28-31-21 | K02094 | | X1 | C | TB0082Y | A004 | BJ | | 050-099, 162-164, 276 |
| 64H | 20 | | PA | | 7-0 | 28-31-21 | K02094 | | X2 | C | GDX0009 | D.. | 2 | | 050-099, 162-164, 276 |
| 64J | 22 | | PA | | 9-0 | 28-31-21 | D04284J | | 4 | | TB0082Y | A004 | BJ | | 050-099, 155-199, 276-299 |
| 64K | 22 | | PA | | 10-0 | 28-31-21 | TB0088D | | A011 | 2 | TB0082Y | A004 | BJ | | 050-099 |
| 64K | 22 | | PA | | 8-0 | 28-31-21 | K02092 | | X1 | C | TB0082Y | A004 | BJ | | 155-157, 165-199, 277-299 |
| 64K | 22 | | PA | | 11-0 | 28-31-21 | TB0088D | | A011 | 2 | TB0082Y | A004 | BJ | | 162-164, 276 |
| 64M | 24 | | PK | | 5-0 | 36-11-62 | D05602J | | 13 | | D05602J | | 14 | | 050-099 |
| 64M | 24 | | PK | | 5-0 | 36-11-62 | D05602J | | 14 | | D05602J | | 13 | | 150-156, 162-166, 275-276 |

WIRE LIST
D280T132

91-21-11
Section W0190
Page 34
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | |
| 64N | 20 | PA | | 3-0 | 36-11-62 | D01993 | A2 | | | | GDX0003 | D.. | 2 | | 050-099, 150-156, 162-166 | |
| 64N | 20 | PA | | 3-0 | 36-11-62 | GDX0003 | D.. | 2 | | | D01993 | A2 | | | 275-276 | |
| 64P | 24 | PK | | 2-0 | 36-11-62 | D01993 | A3 | | | | D01999 | X2 | | | 050-099 | |
| 64P | 24 | PK | | 3-0 | 36-11-62 | D01993 | A3 | | | | D01999 | X2 | | | 150-156, 162-166, 275-276 | |
| 64R | 24 | PK | | 3-0 | 36-11-62 | D01993 | X1 | | | | TB0254Z | 14 | BJ | | 050-099, 275-276 | |
| 64R | 24 | PK | | 4-0 | 36-11-62 | D01993 | X1 | | | | TB0254Z | 14 | BJ | | 150-156, 162-166 | |
| 650 | 22 | PA | | 5-0 | 49-61-11 | D03700 | | 1 | | | TB0212X | A002 | BJ | | ALL | |
| 652 | 24 | PK | | 4-0 | 21-61-11 | D05612J | | 54 | | | D03678 | B2 | | | ALL | |
| 653 | 24 | PK | | 4-0 | 21-61-11 | D05612J | | 55 | | | D03678 | C1 | | | ALL | |
| 654 | 22 | PA | | 4-0 | 28-42-11 | D04646J | | 13 | | | TB0304Y | A014 | BJ | | ALL | |
| 655 | 22 | PA | | 3-0 | 27-81-21 | D10014 | X1 | | | | TB0082G | 10 | 2 | | 050-099, 150-199, 275-278 | |
| 655 | 22 | PA | | 4-0 | 27-81-21 | D10014 | X1 | | | | TB0082G | 10 | 2 | | 280-299 | |
| 656 | 22 | PA | | 9-0 | 27-81-21 | D10014 | X2 | | | | D05316J | 2 | | | ALL | |
| 65G | 24 | PK | | 3-0 | 36-11-62 | D01999 | A1 | | | | TB0254Z | 14 | BJ | | 050-099, 275-276 | |
| 65G | 24 | PK | | 4-0 | 36-11-62 | TB0254Z | | 14 | BJ | | D01999 | A1 | | | 150-156, 162-166 | |
| 65H | 24 | PK | | 3-0 | 36-11-62 | D01999 | A2 | | | | TB0254Y | C004 | BJ | | 050-099, 275-276 | |
| 65H | 24 | PK | | 4-0 | 36-11-62 | TB0254Y | | C004 | BJ | | D01999 | A2 | | | 150-156, 162-166 | |
| 65J | 24 | PK | | 5-0 | 36-11-62 | D01999 | B1 | | | | TB0212Y | A011 | BJ | | 050-099, 275-276 | |
| 65J | 24 | PK | | 6-0 | 36-11-62 | TB0212Y | | A011 | BJ | | D01999 | B1 | | | 150-155, 162-165 | |
| 65J | 24 | PK | | 5-0 | 36-11-62 | TB0212Y | | A011 | BJ | | D01999 | B1 | | | 156, 166 | |
| 65K | 20 | PA | | 3-0 | 36-11-62 | D01999 | B2 | | | | GDX0003 | D.. | 2 | | 050-099, 150-156, 162-166 | |
| 65K | 20 | PA | | 3-0 | 36-11-62 | GDX0003 | D.. | 2 | | | D01999 | B2 | | | 275-276 | |
| 65L | 24 | PK | | 3-0 | 36-11-62 | D01999 | X1 | | | | TB0254Y | C004 | BJ | | 050-099, 275-276 | |
| 65L | 24 | PK | | 4-0 | 36-11-62 | TB0254Y | | C004 | BJ | | D01999 | X1 | | | 150-156, 162-166 | |
| 65M | 24 | PK | | 3-0 | 36-11-62 | D02001 | A1 | | | | TB0254Z | 14 | BJ | | 050-099, 275-276 | |
| 65M | 24 | PK | | 4-0 | 36-11-62 | D02001 | A1 | | | | TB0254Z | 14 | BJ | | 150-156, 162-166 | |
| 65N | 24 | PK | | 3-0 | 36-11-62 | D02001 | A2 | | | | TB0254Y | C004 | BJ | | 050-099 | |
| 65N | 24 | PK | | 4-0 | 36-11-62 | D02001 | A2 | | | | TB0254Y | C004 | BJ | | 150-155, 162-165 | |
| 65N | 24 | PK | | 4-0 | 36-11-62 | TB0254Y | | C004 | BJ | | D02001 | A2 | | | 156, 166 | |
| 65N | 24 | PK | | 3-0 | 36-11-62 | TB0254Y | | C004 | BJ | | D02001 | A2 | | | 275-276 | |
| 65P | 24 | PK | | 10-0 | 36-11-62 | D10158 | A2 | | | | D06076J | 17 | | | 050-099 | |
| 65P | 24 | PK | | 10-0 | 36-11-62 | D06076J | | 17 | | | D10158 | A2 | | | 150-156, 162-166, 275-276 | |
| 65P | 24 | PK | | 6-0 | 36-11-62 | D06076J | | 17 | | | D10158 | A2 | | | 157, 167-199 | |
| 65P | 24 | PK | | 6-0 | 36-11-62 | D10158 | | A2 | | | D06076J | 17 | | | 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 35

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 65Q | 24 | | PK | | 4-0 | 36-11-62 | TB0212Y | A011 | BJ | | TB0086D | A006 | 2 | | 050-099 |
| 65Q | 24 | | PK | | 4-0 | 36-11-62 | TB0086D | A006 | 2 | | TB0212Y | A011 | BJ | | 150-155, 163-165, 275-276 |
| 65Q | 24 | | PK | | 8-0 | 36-11-62 | TB0212Y | A011 | BJ | | TB0086D | A006 | 2 | | 156, 166 |
| 65Q | 24 | | PK | | 10-0 | 36-11-62 | TB0212Y | A011 | BJ | | TB0086D | A006 | 2 | | 162 |
| 65R | 20 | | PA | | 3-0 | 36-11-62 | D02001 | | B2 | | GDX0003 | D.. | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 65T | 24 | | PK | | 10-0 | 36-11-62 | TB0314Z | | 6 | BJ | TB0254Z | | 14 | BJ | 050-099, 275-276 |
| 65T | 24 | | PK | | 10-0 | 36-11-62 | TB0254Z | | 14 | BJ | TB0314Z | | 6 | BJ | 150-156, 162-166 |
| 65U | 24 | | PK | | 6-0 | 36-11-62 | D05768J | | 23 | | TB0274G | | 42 | 2 | 050-099 |
| 65U | 24 | | PK | | 6-0 | 36-11-62 | D05768J | | 23 | | TB0212Y | C012 | BJ | | 150-154 |
| 65U | 24 | | PK | | 5-0 | 36-11-62 | D05768J | | 23 | | TB0274G | | 42 | 2 | 155-156, 162-166, 276 |
| 65U | 24 | | PK | | 10-0 | 36-11-62 | D05768J | | 23 | | TB0314Y | A005 | BJ | | 157, 167-199, 277-299 |
| 65U | 24 | | PK | | 5-0 | 36-11-62 | D05768J | | 23 | | TB0212Y | C012 | BJ | | 275 |
| 65V | 24 | | PK | | 3-0 | 36-11-62 | D02001 | | X1 | | TB0254Z | | 14 | BJ | 050-099, 275-276 |
| 65V | 24 | | PK | | 4-0 | 36-11-62 | D02001 | | X1 | | TB0254Z | | 14 | BJ | 150-156, 162-166 |
| 65W | 24 | | PK | | 10-0 | 36-11-62 | D05068J | | 16 | | TB0086D | C006 | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 65Y | 24 | | PK | | 5-0 | 36-11-62 | D06076J | | 9 | | TB0274G | | 42 | 2 | 050-099, 155-156, 162-166 |
| 65Y | 24 | | PK | | 10-0 | 36-11-62 | D06076J | | 9 | | TB0212Y | C012 | BJ | | 150-154, 275 |
| 65Y | 24 | | PK | | 10-0 | 36-11-62 | D06076J | | 9 | | TB0314Y | A005 | BJ | | 157, 167-199, 277-299 |
| 65Y | 24 | | PK | | 7-0 | 36-11-62 | D06076J | | 9 | | TB0274G | | 42 | 2 | 276 |
| 660 | 24 | | PK | | 6-0 | 21-26-21 | D05352J | | 2 | | TB0274Y | C010 | BJ | | ALL |
| 661 | 22 | | PA | | 6-0 | 21-26-21 | D05352J | | 3 | | D01006 | | D2 | | ALL |
| 662 | 24 | | PK | | 3-0 | 21-44-21 | D05352J | | 23 | | D05688J | | 13 | | ALL |
| 663 | 24 | | PK | | 3-0 | 21-44-21 | D05352J | | 24 | | D05688J | | 14 | | ALL |
| 664 | 24 | | PK | | 5-0 | 21-26-21 | D01006 | | X1 | | TB0274Y | C010 | BJ | | ALL |
| 667 | 20 | | PA | | 8-0 | 21-26-21 | D12240 | | 13 | | GDX0003 | S.. | 2 | | 050-099 |
| 667 | 20 | | PA | | 3-0 | 21-26-21 | D01006 | | B2 | | GDX0003 | S.. | 2 | | 150-154, 275 |
| 667 | 20 | | PA | | 7-0 | 21-26-21 | D12240 | | 13 | | GDX0003 | S.. | 2 | | 155-199, 276-299 |
| 66A | 24 | | PK | | 2-0 | SPARE | TB0274D | | CAP | Y | TB0274Y | C011 | BJ | | 050-099 |
| 66A | 24 | | PK | | 3-0 | SPARE | TB0274D | | C002 | 2 | TB0274Y | C011 | BJ | | 150-154, 275-276 |
| 66A | 24 | | PK | | 3-0 | SPARE | TB0274D | | CAP | Y | TB0274Y | C011 | BJ | | 155-156, 162-166 |
| 66D | 20 | | PQ | EL | 8-0 | 28-31-12 | D12166 | | 2 | | GDX0006 | D.. | 2 | *1 | 050-099 |
| 66D | 20 | | PQ | EL | 8-0 | 28-31-12 | D12166 | | 2 | | GDX0013 | D.. | 2 | * | 155-199 |
| 66D | 20 | | PQ | EL | 8-0 | 28-31-12 | D12166 | | 2 | | GDX0013 | D.. | 2 | | 276-299 |
| 66DZ | | | | EL | 0-0 | 28-31-12 | D12166 | | DED | | GDX0006 | DED | | | 050-099 |
| 66DZ | | | | EL | 0-0 | 28-31-12 | D12166 | | DED | | GDX0013 | DED | | | 155-199, 276-299 |

WIRE LIST
D280T132

91-21-11
Section W0190
Page 36
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 66E | 22 | | PA | | 7-0 | 28-31-12 | D05068J | | 42 | | | | D12166 | | 3 | | 050-099, 155-199, 276-299 |
| 66G | 22 | | PQ | EM | 8-0 | 28-31-12 | D12166 | | 4 | | | | TB0304D | C037 | 2 | | 050-099, 155-199, 276-299 |
| 66GZ | | | | EM | 0-0 | 28-31-12 | D12166 | | DED | | | | TB0304D | DED | | | 050-099, 155-199, 276-299 |
| 66H | 20 | | PA | | 8-0 | 28-31-12 | D12166 | | 7 | | | | GDX0006 | D.. | 2 | *1 | 050-099 |
| 66H | 20 | | PA | | 8-0 | 28-31-12 | D12166 | | 7 | | | | GDX0013 | D.. | 2 | * | 155-199 |
| 66H | 20 | | PA | | 8-0 | 28-31-12 | D12166 | | 7 | | | | GDX0013 | D.. | 2 | | 276-299 |
| 66J | 22 | | PQ | EN | 5-0 | 28-31-12 | D04284J | | 9 | | | | TB0304D | C037 | 2 | | 050-099 |
| 66J | 22 | | PQ | EN | 4-0 | 28-31-12 | D04284J | | 9 | | | | TB0304D | C037 | 2 | | 155-199, 276-299 |
| 66JZ | | | | EN | 0-0 | 28-31-12 | D04284J | | DED | | | | TB0304D | DED | | | 050-099, 155-199, 276-299 |
| 66L | 20 | | PA | | 5-0 | 28-31-12 | D05068J | | 41 | | | | D04284J | | 11 | | 050-099 |
| 66L | 20 | | PA | | 2-0 | 28-31-12 | D05068J | | 41 | | | | D04284J | | 11 | | 155-199, 276-299 |
| 66M | 20 | | PA | | 5-0 | 28-31-12 | D05068J | | 40 | | | | D04284J | | 10 | | 050-099 |
| 66M | 20 | | PA | | 2-0 | 28-31-12 | D05068J | | 40 | | | | D04284J | | 10 | | 155-199, 276-299 |
| 66W | 22 | | PQ | FS | 5-0 | 28-31-12 | D04284J | | 16 | | | | TB0320Y | C012 | BJ | | 050 |
| 66W | 22 | | PQ | FS | 20-0 | 28-31-12 | D04284J | | 16 | | | | TB0212Y | A014 | BJ | | 051-099 |
| 66W | 22 | | PQ | FS | 5-0 | 28-31-12 | D04284J | | 16 | | | | TB0212Y | CAP | Y | | 155-157, 165-199, 277-299 |
| 66W | 22 | | PQ | FS | 5-0 | 28-31-12 | D04284J | | 16 | | | | TB0212Y | A014 | BJ | | 162-164 |
| 66WZ | | | | FS | 0-0 | 28-31-12 | D04284J | | DED | | | | TB0320Y | DED | | | 050 |
| 66WZ | | | | FS | 0-0 | 28-31-12 | D04284J | | DED | | | | TB0212Y | DED | | | 051-099, 155-199, 277-299 |
| 66X | 22 | | PQ | FU | 2-0 | 28-31-12 | TB0320Y | | C012 | BJ | | | TB0304D | A037 | 2 | | 050 |
| 66X | 22 | | PQ | FU | 20-0 | 28-31-12 | TB0212Y | | A014 | BJ | | | TB0304D | A037 | 2 | | 051-099 |
| 66X | 22 | | PQ | FU | 8-0 | 28-31-12 | TB0212Y | | A014 | BJ | | | TB0304D | A037 | 2 | | 155-199, 277-299 |
| 66XZ | | | | FU | 0-0 | 28-31-12 | TB0320Y | | DED | | | | TB0304D | DED | | | 050 |
| 66XZ | | | | FU | 0-0 | 28-31-12 | TB0212Y | | DED | | | | TB0304D | DED | | | 051-099, 155-199, 277-299 |
| 674 | 24 | | PK | | 3-0 | 29-33-11 | D04346J | | 37 | | | | D05352J | | 46 | | ALL |
| 677 | 22 | | PA | | 4-0 | 29-33-11 | TB0304Y | | A016 | BJ | | | D05352J | | 47 | | ALL |
| 67A | 22 | | PQ | EH | 8-0 | 28-31-11 | D12162 | | A2 | | | | TB0304Y | A026 | BJ | | 050-099, 155-199, 276-299 |
| 67AZ | | | | EH | 0-0 | 28-31-11 | D12162 | | DED | | | | TB0304Y | DED | | | 050-099, 155-199, 276-299 |
| 67B | 20 | | PQ | EI | 8-0 | 28-31-11 | D12162 | | A3 | | | | GDX0006 | D.. | 2 | *2 | 050-099 |
| 67B | 20 | | PQ | EI | 8-0 | 28-31-11 | D12162 | | A3 | | | | GDX0013 | D.. | 2 | | 155-199, 276-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 37

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 67BZ | | | | EI | 0-0 | 28-31-11 | D12162 | | DED | | GDX0006 | DED | | | 050-099 |
| 67BZ | | | | EI | 0-0 | 28-31-11 | D12162 | | DED | | GDX0013 | DED | | | 155-199, 276-299 |
| 67C | 22 | PA | | | 7-0 | 28-31-11 | D05068J | | 11 | | D12162 | C1 | | | 050-099, 155-199, 276-299 |
| 67D | 22 | PA | | | 7-0 | 28-31-11 | D04284J | | 6 | | D12162 | X1 | | | 050-099, 155-199, 276-299 |
| 67E | 20 | PA | | | 8-0 | 28-31-11 | D12162 | | X2 | | GDX0006 | D.. | 2 | *2 | 050-099 |
| 67E | 20 | PA | | | 8-0 | 28-31-11 | D12162 | | X2 | | GDX0013 | D.. | 2 | | 155-199, 276-299 |
| 67F | 22 | PQ | EK | | 6-0 | 28-31-11 | D04284J | | 3 | | TB0304Y | A026 | BJ | | 050-099 |
| 67F | 22 | PQ | EK | | 4-0 | 28-31-11 | D04284J | | 3 | | TB0304Y | A026 | BJ | | 155-199, 276-299 |
| 67FZ | | | | EK | 0-0 | 28-31-11 | D04284J | | DED | | TB0304Y | DED | | | 050-099, 155-199, 276-299 |
| 67G | 22 | PQ | EJ | | 3-0 | 28-31-11 | D05374J | | 1 | | TB0304Y | A026 | BJ | | 050-099, 155-199, 276-299 |
| 67GZ | | | | EJ | 0-0 | 28-31-11 | D05374J | | DED | | TB0304Y | DED | | | 050-099, 155-199, 276-299 |
| 67H | 20 | PA | | | 5-0 | 28-31-11 | D05068J | | 38 | | D04284J | 7 | | | 050-099 |
| 67H | 20 | PA | | | 2-0 | 28-31-11 | D05068J | | 38 | | D04284J | 7 | | | 155-199, 276-299 |
| 67J | 20 | PA | | | 5-0 | 28-31-11 | D05068J | | 37 | | D04284J | 8 | | | 050-099 |
| 67J | 20 | PA | | | 2-0 | 28-31-11 | D05068J | | 37 | | D04284J | 8 | | | 155-199, 276-299 |
| 67K | 22 | PQ | CM | | 12-0 | 73-21-11 | D12248 | | 5 | | D12252 | X2 | | | 050-099 |
| 67K | 22 | PQ | EE | | 12-0 | 73-21-11 | D12248 | | 5 | | D12252 | X2 | | | 150-154, 275-276 |
| 67K | 22 | PQ | EE | | 11-0 | 73-21-11 | D12248 | | 5 | | D12252 | X2 | | | 155-157 |
| 67K | 22 | PQ | EE | | 6-0 | 73-21-11 | D12248 | | 5 | | D12252 | X2 | | | 162-199 |
| 67K | 22 | PQ | EE | | 7-0 | 73-21-11 | D12248 | | 5 | | D12252 | X2 | | | 277-299 |
| 67KZ | | | | CM | 0-0 | 73-21-11 | D12248 | | DED | | D12252 | DED | | | 050-099 |
| 67KZ | | | | EE | 0-0 | 73-21-11 | D12248 | | DED | | D12252 | DED | | | 150-199, 275-299 |
| 67L | 22 | PQ | EY | | 8-0 | 73-21-11 | D12252 | | X1 | | TB0304H | 29 | 2 | | 050-099 |
| 67L | 22 | PQ | EF | | 8-0 | 73-21-11 | D12252 | | X1 | | TB0304H | 29 | 2 | | 150-157, 275-276 |
| 67L | 22 | PQ | EF | | 9-0 | 73-21-11 | D12252 | | X1 | | TB0304H | 29 | 2 | | 162-199, 277-299 |
| 67LZ | | | | EY | 0-0 | 73-21-11 | D12252 | | DED | | TB0304H | DED | | | 050-099 |
| 67LZ | | | | EF | 0-0 | 73-21-11 | D12252 | | DED | | TB0304H | DED | | | 150-199, 275-299 |
| 67M | 20 | PA | | | 8-0 | 73-21-11 | D12252 | | A1 | | TB0304Y | C019 | BJ | | 050-099 |
| 67M | 20 | PA | | | 8-0 | 73-21-11 | D12252 | | A1 | | TB0304Y | C020 | BJ | | 150-157, 275-276 |
| 67M | 20 | PA | | | 9-0 | 73-21-11 | D12252 | | A1 | | TB0304Y | C020 | BJ | | 162-199 |
| 67M | 20 | PA | | | 9-0 | 73-21-11 | D12252 | | A1 | | TB0304Y | C019 | BJ | | 277-299 |
| 67N | 22 | PQ | FA | | 8-0 | 73-21-11 | D12252 | | Y1 | | TB0304H | 29 | 2 | | 050-099 |
| 67N | 22 | PQ | EG | | 8-0 | 73-21-11 | D12252 | | Y1 | | TB0304H | 29 | 2 | | 150-157, 275-276 |
| 67N | 22 | PQ | EG | | 9-0 | 73-21-11 | D12252 | | Y1 | | TB0304H | 29 | 2 | | 162-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 38

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 67NZ | | | | FA | 0-0 | 73-21-11 | D12252 | | DED | | TB0304H | DED | | | 050-099 |
| 67NZ | | | | EG | 0-0 | 73-21-11 | D12252 | | DED | | TB0304H | DED | | | 150-199, 275-299 |
| 67P | 20 | PA | | | 2-0 | 73-21-11 | D12252 | | A2 | | GDX0003 | D.. | 2 | | 050-099, 150-154, 275-276 |
| 67P | 20 | PA | | | 3-0 | 73-21-11 | D12252 | | A2 | | GDX0003 | D.. | 2 | | 155-157 |
| 67P | 20 | PA | | | 9-0 | 73-21-11 | D12252 | | A2 | | GDX0003 | D.. | 2 | | 162-199, 277-299 |
| 67R | 22 | PQ | CN | | 2-0 | 73-21-11 | D12252 | | Y2 | | D11754 | B1 | | | 050-099 |
| 67R | 22 | PQ | EW | | 2-0 | 73-21-11 | D12252 | | Y2 | | D11754 | B1 | | | 150-157, 275-276 |
| 67R | 22 | PQ | EW | | 9-0 | 73-21-11 | D12252 | | Y2 | | D11754 | B1 | | | 162-199, 277-299 |
| 67RZ | | | CN | | 0-0 | 73-21-11 | D12252 | | DED | | D11754 | DED | | | 050-099 |
| 67RZ | | | EW | | 0-0 | 73-21-11 | D12252 | | DED | | D11754 | DED | | | 150-199, 275-299 |
| 67T | 20 | PA | | | 8-0 | 73-21-11 | D00640 | | 9 | | D11754 | B2 | | | ALL |
| 67U | 20 | PA | | | 3-0 | 73-21-11 | D00640 | | 11 | | GDX0005 | D.. | 2 | | ALL |
| 67V | 20 | PA | | | 9-0 | 73-21-11 | D00640 | | 10 | | TB0304Y | C019 | BJ | | 050-099, 277-299 |
| 67V | 20 | PA | | | 9-0 | 73-21-11 | D00640 | | 10 | | TB0304Y | C020 | BJ | | 150-199, 275-276 |
| 67W | 20 | PA | | | 8-0 | 73-21-11 | D13626 | | X2 | | TB0304Y | C019 | BJ | | 050-099, 277-299 |
| 67W | 20 | PA | | | 8-0 | 73-21-11 | D13626 | | X2 | | TB0304Y | C020 | BJ | | 150-199, 275-276 |
| 67X | 20 | PA | | | 8-0 | 73-21-11 | D13626 | | X1 | | TB0304H | 29 | 2 | | ALL |
| 67Y | 16 | PQ | BM | | 7-0 | 73-21-11 | D13626 | | A1 | | D05328J | 16 | FL | | 050-099 |
| 67Y | 16 | PQ | EX | | 7-0 | 73-21-11 | D13626 | | A1 | | D05328J | 16 | FL | | 150-154, 275-276 |
| 67Y | 16 | PQ | EX | | 8-0 | 73-21-11 | D13626 | | A1 | | D05328J | 16 | FL | | 155-199, 277-299 |
| 67YZ | | | BM | | 0-0 | 73-21-11 | D13626 | | | FD | D05328J | 11 | | | 050-099 |
| 67YZ | | | EX | | 0-0 | 73-21-11 | D13626 | | | FD | D05328J | 11 | | | 150-199, 275-299 |
| 680 | 22 | PA | | | 10-0 | 36-11-62 | D06076J | | 24 | | TB0190Y | A011 | BJ | | 050-099, 150-155, 162-165, 275-276 |
| 680 | 22 | PA | | | 7-0 | 36-11-62 | D06076J | | 24 | | TB0320Y | A019 | BJ | | 156, 166 |
| 680 | 22 | PA | | | 5-0 | 36-11-62 | D06076J | | 24 | | TB0320Y | A019 | BJ | | 157, 167-199, 277-299 |
| 681 | 22 | PA | | | 10-0 | 36-11-62 | D06076J | | 23 | | TB0190Y | C011 | BJ | | 050-099, 150-155, 162-165, 275-276 |
| 681 | 22 | PA | | | 7-0 | 36-11-62 | D06076J | | 23 | | TB0320Y | C019 | BJ | | 156, 166 |
| 681 | 22 | PA | | | 5-0 | 36-11-62 | D06076J | | 23 | | TB0320Y | C019 | BJ | | 157, 167-199, 277-299 |
| 682 | 24 | PK | | | 5-0 | 36-11-62 | D06076J | | 22 | | TB0212Y | A011 | BJ | | 050-099, 150-156, 162-166, 275-276 |
| 682 | 24 | PK | | | 5-0 | 36-11-62 | D06076J | | 22 | | TB0320Y | A009 | BJ | | 157, 167-199, 277-299 |
| 683 | 24 | PK | | | 3-0 | 36-11-62 | D05068J | | 13 | | D06076J | 21 | | | 050-099 |
| 683 | 24 | PK | | | 4-0 | 36-11-62 | D05068J | | 13 | | D06076J | 21 | | | 150-199 |
| 683 | 24 | PK | | | 3-0 | 36-11-62 | D06076J | | 21 | | D05068J | 13 | | | 275-299 |
| 684R | 22 | PH | | | 4-0 | 26-18-22 | D05602J | | 7 | | D05068J | 18 | | | 050-099 |
| 684R | 22 | PA | | | 5-0 | 26-18-22 | D05602J | | 7 | | D05068J | 18 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 39

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|-----------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 684R | 22 | | PH | | 3-0 | 26-18-22 | D05602J | | 7 | | | | D05068J | 18 | | | 275-299 |
| 685R | 22 | | PH | | 4-0 | 26-18-22 | D05602J | | 8 | | | | D05068J | 30 | | | 050-099 |
| 685R | 22 | | PH | | 5-0 | 26-18-22 | D05602J | | 8 | | | | D05068J | 30 | | | 150-199 |
| 685R | 22 | | PH | | 3-0 | 26-18-22 | D05602J | | 8 | | | | D05068J | 30 | | | 275-299 |
| 687 | 20 | | PA | | 9-0 | 30-71-24 | D03748 | | A1 | | | | D05688J | 3 | | | 150-199 |
| 68A | 16 | | PA | | 8-0 | 73-21-11 | D13626 | | A2 | | | | TB0304H | 29 | 2 | | 050-099, 150-157, 275-299 |
| 68A | 16 | | PA | | 2-0 | 73-21-11 | D13626 | | A2 | | | | TB0304H | 29 | 2 | | 162-199 |
| 68B | 20 | | UA | | 3-0 | 73-21-11 | D13626 | | | | | FD | GDX0003 | S.. | 2 | | ALL |
| 68C | 16 | | PA | | 4-0 | 73-21-11 | D05328J | | | FL | | | TB0304H | 29 | 2 | | ALL |
| 68D | 20 | | PA | | 4-0 | 73-21-11 | D05328J | | 7 | | | | TB0304Y | C019 | BJ | | 050-099, 277-299 |
| 68D | 20 | | PA | | 4-0 | 73-21-11 | D05328J | | 7 | | | | TB0304Y | C020 | BJ | | 150-199, 275-276 |
| 68E | 20 | | PA | | 12-0 | 73-21-11 | D12248 | | 2 | | | | GDX0003 | D.. | 2 | | 050-099, 150-154, 275-276 |
| 68E | 20 | | PA | | 11-0 | 73-21-11 | D12248 | | 2 | | | | GDX0003 | D.. | 2 | | 155-199, 277-299 |
| 68W | 24 | | PK | | 10-0 | 32-09-12 | D20100 | | X1 | | | | TB0084Y | C002 | BJ | | ALL |
| 68X | 24 | | PK | | 10-0 | 32-09-12 | D20100 | | X2 | | | | TB0082Y | A002 | BJ | | ALL |
| 68Y | 24 | | PK | | 3-0 | 32-09-12 | TB0082Z | | 7 | BJ | | | TB0082Y | A002 | BJ | | ALL |
| 690 | 24 | | PK | | 8-0 | 21-61-21 | D05612J | | 56 | | | | D03716 | B2 | | | ALL |
| 691 | 20 | | PA | | 4-0 | 27-61-18 | D05317J | | 6 | | | | D05660J | 8 | | | ALL |
| 692 | 20 | | PA | | 4-0 | 27-61-18 | D05317J | | 7 | | | | D05660J | 7 | | | ALL |
| 693 | 18 | | PA | | 3-0 | 38-32-14 | D04284J | | 5 | DK | | | D05688J | 24 | DK | | ALL |
| 696 | 24 | | PK | | 9-0 | 21-26-11 | D05352J | | 11 | | | | TB0082Y | C001 | BJ | | ALL |
| 698 | 24 | | PK | | 9-0 | 32-09-13 | TB0084Z | | 13 | BJ | | | D05290J | 17 | | | ALL |
| 699 | 24 | | PK | | 8-0 | 21-61-21 | D05612J | | 57 | | | | D03716 | C1 | | | ALL |
| 69A | 20 | | PQ | HC | 12-0 | 78-34-11 | D20100 | | A1 | | | | D04284J | 25 | | | ALL |
| 69AZ | | | | HC | 0-0 | 78-34-11 | D20100 | | DED | | | | D04284J | | | HC | ALL |
| 69B | 20 | | PQ | HE | 12-0 | 78-34-11 | D20100 | | A2 | | | | D04284J | 24 | | | ALL |
| 69BZ | | | | HE | 0-0 | 78-34-11 | D20100 | | DED | | | | D04284J | | | HC | ALL |
| 69D | 24 | | PK | | 12-0 | 78-36-21 | D05068J | | 49 | | | | D10088 | 1 | | | ALL |
| 69F | 20 | | PA | | 5-0 | 78-36-21 | D03690 | | 9 | | | | GDX0016 | D.. | 2 | | ALL |
| 69G | 24 | | PK | | 12-0 | 78-36-21 | D03690 | | 10 | | | | D10090 | 6 | | | ALL |
| 69H | 24 | | PK | | 10-0 | 78-36-21 | D03670 | | A2 | | | | D10088 | 8 | | | 050-099, 157, 167-199, 277-299 |
| 69H | 24 | | PK | | 8-0 | 78-36-21 | D03670 | | A2 | | | | D10088 | 8 | | | 150-156, 162-166, 275-276 |
| 69J | 24 | | PK | | 8-0 | 78-36-21 | D05068J | | 47 | | | | D05326J | 55 | | | 050-099 |
| 69J | 24 | | PK | | 5-0 | 78-36-21 | D05068J | | 47 | | | | D05326J | 55 | | | 150-199, 275-299 |
| 69K | 24 | | PK | | 12-0 | 78-36-21 | D05068J | | 48 | | | | D03690 | 11 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 40

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | |
| 700 | 24 | | PK | 8-0 | 21-61-31 | D05612J | | 58 | | | D03754 | B2 | | | ALL | |
| 701 | 24 | | PK | 8-0 | 21-61-31 | D05612J | | 59 | | | D03754 | C2 | | | ALL | |
| 702 | 24 | | PK | 4-0 | 29-11-12 | D05612J | | 12 | | | M00499 | B | C | | 050-099 | |
| 702 | 24 | | PK | 6-0 | 29-11-12 | D05612J | | 12 | | | M00499 | B | C | | 150-199, 275-299 | |
| 704 | 24 | | PK | 5-0 | 21-58-15 | D05612J | | 30 | | | SP01612 | | W | | ALL | |
| 705 | 18 | | PA | 6-0 | 21-26-11 | D05660J | | 1 | | | K00346 | A1 | E | | ALL | |
| 706 | 18 | | PA | 6-0 | 21-26-11 | D05660J | | 2 | | | K00346 | B1 | E | | ALL | |
| 707 | 18 | | PA | 6-0 | 21-26-11 | D05660J | | 3 | | | K00346 | C1 | E | | ALL | |
| 708 | 20 | | PA | 3-0 | 32-31-11 | D03712 | | A2 | | | GDX0007 | D.. | 2 | | ALL | |
| 709 | 24 | | PK | 3-0 | 32-09-12 | D03712 | | X1 | | | TB0084Z | 13 | BJ | | ALL | |
| 70C | 22 | | PQ | T | 8-0 | 21-28-11 | D05602J | | 4 | | TB0314X | C009 | BJ | | 050-099 | |
| 70C | 22 | | PA | | 9-0 | 21-28-11 | D05602J | | 4 | | TB0314X | C009 | BJ | | 150-199, 275-299 | |
| 70CZ | | | | T | 0-0 | 21-28-11 | D05602J | | DED | | TB0314X | DED | | | 050-099 | |
| 70F | 22 | | PA | | 5-0 | 21-45-22 | D05688J | | 12 | | D05266J | 7 | | | 050-099, 155-199, 276-299 | |
| 70F | 22 | | PA | | 8-0 | 21-45-22 | D05688J | | 12 | | D05266J | 7 | | | 150-154, 275 | |
| 70K | 24 | | PK | | 8-0 | 21-61-81 | D13440 | | B2 | | TB0304Y | A013 | BJ | | 050-099, 275-299 | |
| 70K | 24 | | PK | | 10-0 | 21-61-81 | D13440 | | B2 | | TB0304Y | A013 | BJ | | 150-199 | |
| 70M | 24 | | PK | | 8-0 | 21-61-81 | D13440 | | D2 | | TB0304Y | A013 | BJ | | 050-099, 275-299 | |
| 70M | 24 | | PK | | 10-0 | 21-61-81 | D13440 | | D2 | | TB0304Y | A013 | BJ | | 150-199 | |
| 70N | 20 | | PA | | 12-0 | 76-11-11 | D11756 | | B2 | | GDX0006 | D.. | 2 | | ALL | |
| 70P | 20 | | PA | | 6-0 | 76-11-11 | D11756 | | B1 | | TB0274D | C021 | 2 | | ALL | |
| 70R | 24 | | PK | | 1-0 | 21-26-11 | TB0088D | | C014 | 2 | TB0088D | C015 | 2 | | 050-099, 155-199, 276-299 | |
| 70S | 24 | | PK | | 8-0 | 21-26-11 | TB0088D | | C015 | 2 | K02092 | 12 | C | | 050-099, 155-199, 276-299 | |
| 70U | 24 | | PK | | 7-0 | 21-58-14 | D05612J | | 5 | | TB0254Y | A009 | BJ | | 050-099, 155-199, 276-299 | |
| 710 | 24 | | PK | | 8-0 | 32-09-12 | D03712 | | X2 | | TB0082Z | 8 | BJ | | ALL | |
| 711 | 24 | | PK | | 3-0 | 32-09-12 | D03698 | | 6 | | TB0084Z | 13 | BJ | | ALL | |
| 712 | 24 | | PK | | 7-0 | 32-09-12 | D03698 | | 12 | | TB0082Z | 8 | BJ | | ALL | |
| 714 | 24 | | PK | | 3-0 | 29-11-12 | D00614 | | B1 | | TB0082Y | C004 | BJ | | ALL | |
| 715 | 24 | | PK | | 3-0 | 29-11-12 | D00614 | | B2 | | TB0082Z | 14 | BJ | | ALL | |
| 716 | 22 | | PA | | 6-0 | 29-11-12 | D00614 | | C3 | | TB0274D | A018 | 2 | | ALL | |
| 717 | 24 | | PK | | 3-0 | 29-11-12 | D00614 | | X1 | | TB0082Z | 14 | BJ | | ALL | |
| 718 | 24 | | PK | | 10-0 | 29-11-12 | D00614 | | X2 | | M00301 | A | C | | ALL | |
| 719 | 24 | | PK | | 2-0 | 29-11-12 | D00618 | | A2 | | D00614 | A1 | | | ALL | |
| 71A | 22 | | PA | | 7-0 | 36-11-52 | SM00025 | | | 9 | TB0314Z | 6 | BJ | | 050-099 | |
| 71A | 22 | | PA | | 5-0 | 36-11-52 | SM00025 | | | 9 | TB0314Z | 6 | BJ | | 150-156, 166 | |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 41

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|------|----|--|---------------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | | | |
| 71A | 22 | | PA | | 8-0 | 36-11-52 | SM00025 | | | | 9 | | | | TB0314Z | 6 | BJ | | 162-165, 275-276 |
| 71B | 22 | | PA | | 5-0 | 36-11-52 | TB0314Z | | 6 | | BJ | | | | D11894 | 3 | | | 050-099 |
| 71B | 22 | | PA | | 4-0 | 36-11-52 | D11894 | | 3 | | | | | | TB0314Z | 6 | BJ | | 150-156, 162-166, 276 |
| 71B | 22 | | PA | | 3-0 | 36-11-52 | D11894 | | 3 | | | | | | TB0314Z | 6 | BJ | | 275 |
| 71C | 22 | | PA | | 5-0 | 36-11-52 | TB0314Z | | 6 | | BJ | | | | D11894 | 6 | | | 050-099 |
| 71C | 22 | | PA | | 4-0 | 36-11-52 | D11894 | | 6 | | | | | | TB0314Z | 6 | BJ | | 150-156, 162-166, 276 |
| 71C | 22 | | PA | | 3-0 | 36-11-52 | D11894 | | 6 | | | | | | TB0314Z | 6 | BJ | | 275 |
| 71D | 22 | | PA | | 5-0 | 36-11-52 | SM00025 | | | | 9 | | | | D11896 | 3 | | | 050-099 |
| 71D | 22 | | PA | | 5-0 | 36-11-52 | D11896 | | 3 | | | | | | SM00025 | | 9 | | 150-156, 162-166 |
| 71D | 22 | | PA | | 8-0 | 36-11-52 | D11896 | | 3 | | | | | | SM00025 | | 9 | | 275-276 |
| 71E | 22 | | PA | | 5-0 | 36-11-52 | SM00025 | | | | 9 | | | | D11896 | | 6 | | 050-099 |
| 71E | 22 | | PA | | 5-0 | 36-11-52 | D11896 | | 6 | | | | | | SM00025 | | 9 | | 150-156, 162-166 |
| 71E | 22 | | PA | | 8-0 | 36-11-52 | D11896 | | 6 | | | | | | SM00025 | | 9 | | 275-276 |
| 71F | 22 | | PA | | 3-0 | 36-11-52 | D11896 | | 1 | | | | | | TB0314Y | A003 | BJ | | 050-099, 275-276 |
| 71F | 22 | | PA | | 4-0 | 36-11-52 | D11896 | | 1 | | | | | | TB0314Y | A003 | BJ | | 150-156, 162-166 |
| 71G | 20 | | PA | | 8-0 | 36-11-52 | TB0314Y | | A003 | | BJ | | | | D05068J | 33 | | | 050-099, 275-299 |
| 71G | 20 | | PA | | 9-0 | 36-11-52 | D05068J | | 33 | | | | | | TB0314Y | A003 | BJ | | 150-199 |
| 71H | 22 | | PA | | 3-0 | 36-11-52 | D11894 | | 1 | | | | | | TB0314Y | C003 | BJ | | 050-099, 275-276 |
| 71H | 22 | | PA | | 4-0 | 36-11-52 | D11894 | | 1 | | | | | | TB0314Y | C003 | BJ | | 150-156, 162-166 |
| 71J | 20 | | PA | | 8-0 | 36-11-52 | D05068J | | 32 | | | | | | TB0314Y | C003 | BJ | | 050-099, 275-299 |
| 71J | 20 | | PA | | 9-0 | 36-11-52 | D05068J | | 32 | | | | | | TB0314Y | C003 | BJ | | 150-199 |
| 71K | 20 | | PA | | 8-0 | 36-11-52 | D05768J | | 25 | | | | | | TB0314Y | C003 | BJ | | 050-099, 275-299 |
| 71K | 20 | | PA | | 9-0 | 36-11-52 | D05768J | | 25 | | | | | | TB0314Y | C003 | BJ | | 150-199 |
| 71L | 22 | | PA | | 3-0 | 36-11-62 | D11900 | | 6 | | | | | | TB0314Z | 6 | BJ | | 050-099, 275-276 |
| 71L | 22 | | PA | | 4-0 | 36-11-62 | D11900 | | 6 | | | | | | TB0314Z | 6 | BJ | | 150-156, 162-166 |
| 71M | 22 | | PA | | 3-0 | 36-11-62 | D11900 | | 3 | | | | | | TB0314Z | 6 | BJ | | 050-099, 150-155, 162-165, 275-276 |
| 71M | 22 | | PA | | 4-0 | 36-11-62 | D11900 | | 3 | | | | | | TB0314Z | 6 | BJ | | 156, 166 |
| 71N | 22 | | PA | | 3-0 | 36-11-62 | TB0314Z | | 6 | | BJ | | | | D11898 | 6 | | | 050-099 |
| 71N | 22 | | PA | | 3-0 | 36-11-62 | D11898 | | 6 | | | | | | TB0314Z | 6 | BJ | | 150-155, 162-165, 275-276 |
| 71N | 22 | | PA | | 4-0 | 36-11-62 | D11898 | | 6 | | | | | | TB0314Z | 6 | BJ | | 156, 166 |
| 71P | 22 | | PA | | 3-0 | 36-11-62 | TB0314Z | | 6 | | BJ | | | | D11898 | 3 | | | 050-099 |
| 71P | 22 | | PA | | 3-0 | 36-11-62 | D11898 | | 3 | | | | | | TB0314Z | 6 | BJ | | 150-155, 162-165, 275-276 |
| 71P | 22 | | PA | | 4-0 | 36-11-62 | D11898 | | 3 | | | | | | TB0314Z | 6 | BJ | | 156, 166 |
| 71R | 22 | | PA | | 3-0 | 36-11-62 | D11900 | | 1 | | | | | | TB0314Y | A004 | BJ | | 050-099, 150-155, 162-165, 275-276 |
| 71R | 22 | | PA | | 4-0 | 36-11-62 | D11900 | | 1 | | | | | | TB0314Y | A004 | BJ | | 156, 166 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 42

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | |
| 71S | 20 | | PA | 8-0 | 36-11-62 | TB0314Y | A004 | | BJ | | D04346J | | 16 | | | 050-099 |
| 71S | 20 | | PA | 9-0 | 36-11-62 | D04346J | | 16 | | | TB0314Y | A004 | | BJ | | 150-199 |
| 71S | 20 | | PA | 8-0 | 36-11-62 | D04346J | | 16 | | | TB0314Y | A004 | | BJ | | 275-299 |
| 71T | 22 | | PA | 3-0 | 36-11-62 | TB0314Y | C004 | | BJ | | D11898 | | 1 | | | 050-099 |
| 71T | 22 | | PA | 3-0 | 36-11-62 | D11898 | | 1 | | | TB0314Y | C004 | | BJ | | 150-155, 162-165, 275-276 |
| 71T | 22 | | PA | 4-0 | 36-11-62 | D11898 | | 1 | | | TB0314Y | C004 | | BJ | | 156, 166 |
| 71U | 20 | | PA | 8-0 | 36-11-62 | TB0314Y | C004 | | BJ | | D04346J | | 17 | | | 050-099 |
| 71U | 20 | | PA | 9-0 | 36-11-62 | D04346J | | 17 | | | TB0314Y | C004 | | BJ | | 150-199 |
| 71U | 20 | | PA | 8-0 | 36-11-62 | D04346J | | 17 | | | TB0314Y | C004 | | BJ | | 275-299 |
| 71V | 22 | | PA | 8-0 | 36-11-62 | D06076J | | 19 | | | TB0314Y | C004 | | BJ | | 050-099, 275-299 |
| 71V | 22 | | PA | 9-0 | 36-11-62 | D06076J | | 19 | | | TB0314Y | C004 | | BJ | | 150-199 |
| 71W | 22 | | PA | 8-0 | 36-11-62 | D06076J | | 18 | | | TB0314Y | A004 | | BJ | | 050-099, 275-299 |
| 71W | 22 | | PA | 9-0 | 36-11-62 | D06076J | | 18 | | | TB0314Y | A004 | | BJ | | 150-199 |
| 71X | 20 | | PA | 6-0 | 36-11-62 | D05768J | | 7 | | | TB0314Z | | 5 | BJ | | 050-099 |
| 71X | 20 | | PA | 1-0 | 36-11-52 | D05768J | | 7 | | | TB0314Z | | 5 | BJ | | 150-154, 275 |
| 71X | 20 | | PA | 8-0 | 36-11-62 | D05768J | | 7 | | | TB0314Z | | 5 | BJ | | 155 |
| 71X | 20 | | PA | 9-0 | 36-11-62 | D05768J | | 7 | | | TB0314Z | | 5 | BJ | | 156, 166 |
| 71X | 20 | | PA | 10-0 | 36-11-62 | D05768J | | 7 | | | TB0314Z | | 5 | BJ | | 162-165, 276 |
| 71Y | 22 | | PA | 3-0 | 36-11-62 | D11902 | | 3 | | | TB0314Z | | 5 | BJ | | 050-099, 150-155, 162-165 |
| 71Y | 22 | | PA | 4-0 | 36-11-62 | D11902 | | 3 | | | TB0314Z | | 5 | BJ | | 156, 166 |
| 71Y | 22 | | PA | 3-0 | 36-11-62 | TB0314Z | | 5 | BJ | | D11902 | | 3 | | | 275-276 |
| 720 | 24 | | PK | 3-0 | 29-11-12 | D00618 | | B2 | | | TB0082Y | C004 | | BJ | | ALL |
| 721 | 22 | | PA | 3-0 | 29-11-12 | D00618 | | B3 | | | TB0082D | A012 | 2 | | * | ALL |
| 722 | 24 | | PK | 10-0 | 29-11-12 | D00618 | | X2 | | | M00302 | | A | C | | ALL |
| 724 | 24 | | PK | 4-0 | 21-25-21 | K00416 | | X1 | C | | TB0192Y | A013 | | BJ | | ALL |
| 726 | 20 | | PA | 7-0 | 21-58-15 | SP01614 | | | W | | GDX0009 | | D.. | 2 | | ALL |
| 72A | 22 | | PA | 3-0 | 36-11-62 | D11902 | | 6 | | | TB0314Z | | 5 | BJ | | 050-099, 150-155, 162-165 |
| 72A | 22 | | PA | 4-0 | 36-11-62 | D11902 | | 6 | | | TB0314Z | | 5 | BJ | | 156, 166 |
| 72A | 22 | | PA | 3-0 | 36-11-62 | TB0314Z | | 5 | BJ | | D11902 | | 6 | | | 275-276 |
| 72B | 22 | | PA | 3-0 | 36-11-62 | D11904 | | 6 | | | TB0314Z | | 5 | BJ | | 050-099, 150-155, 162-165 |
| 72B | 22 | | PA | 4-0 | 36-11-62 | D11904 | | 6 | | | TB0314Z | | 5 | BJ | | 156, 166 |
| 72B | 22 | | PA | 3-0 | 36-11-62 | TB0314Z | | 5 | BJ | | D11904 | | 6 | | | 275-276 |
| 72C | 22 | | PA | 3-0 | 36-11-62 | D11904 | | 3 | | | TB0314Z | | 5 | BJ | | 050-099, 150-155, 162-165 |
| 72C | 22 | | PA | 4-0 | 36-11-62 | D11904 | | 3 | | | TB0314Z | | 5 | BJ | | 156, 166 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 43

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------------|----------|---------|------|------|--------|-------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | |
| 72C | 22 | | PA | | 3-0 | 36-11-62 | TB0314Z | | 5 | BJ | | | | | 275-276 |
| 72D | 22 | | PA | | 4-0 | 36-11-62 | D11904 | | 1 | | | | | | 050-099, 150-155, 162-165, 275-276 |
| 72D | 22 | | PA | | 10-0 | 36-11-62 | D11904 | | 1 | | | | | | 156, 166 |
| 72E | 22 | | PA | | 4-0 | 36-11-62 | D11902 | | 1 | | | | | | 050-099, 150-155, 162-165, 275-276 |
| 72E | 22 | | PA | | 10-0 | 36-11-62 | D11902 | | 1 | | | | | | 156, 166 |
| 72F | 20 | | PA | | 8-0 | 36-11-52 | D05768J | | 3 | | | | | | 050-099 |
| 72F | 20 | | PA | | 9-0 | 36-11-52 | D05768J | | 3 | | | | | | 150-199 |
| 72F | 20 | | PA | | 8-0 | 36-11-52 | TB0314Y | | A003 | BJ | | | | | 275-299 |
| 72G | 20 | | PA | | 3-0 | 31-31-11 | D03714 | | D1 | | | | | | ALL |
| 72H | 24 | | PK | | 8-0 | 21-61-81 | TB0274Y | | C029 | BJ | | | | | 050-099 |
| 72H | 24 | | PK | | 6-0 | 21-61-81 | D13438 | | X1 | | | | | | 150 |
| 72H | 24 | | PK | | 7-0 | 21-61-81 | TB0274Y | | C029 | BJ | | | | | 151-199, 275-299 |
| 72J | 24 | | PK | | 9-0 | 21-61-81 | D13440 | | X1 | | | | | | 050-099 |
| 72J | 24 | | PK | | 7-0 | 21-61-81 | D13440 | | X1 | | | | | | 150-199 |
| 72J | 24 | | PK | | 8-0 | 21-61-81 | D13440 | | X1 | | | | | | 275-299 |
| 72L | 24 | | PK | | 8-0 | 21-58-14 | D12242 | | 7 | | | | | | 050-099, 155-199, 276-299 |
| 72M | 24 | | PK | | 8-0 | 21-58-14 | D12242 | | 3 | | | | | | 050-099, 155-199, 276-299 |
| 72N | 24 | | PK | | 4-0 | 21-58-14 | D12242 | | 4 | | | | | | 050-099, 155-199, 276-299 |
| 730 | 24 | | PK | | 2-0 | 21-61-21 | TB0088D | | A001 | 2 | | | | | ALL |
| 732 | 22 | | PA | | 5-0 | 21-61-11 | D03678 | | A1 | | | | | | ALL |
| 733 | 20 | | PA | | 3-0 | 21-61-11 | D03678 | | A2 | | | | | | ALL |
| 735 | 16 | | PA | | 6-0 | 38-13-11 | D05660J | | 5 | | | | | | 050-099 |
| 735 | 16 | | PA | | 6-0 | 38-13-11 | D05660J | | 5 | | | | | | 150-199, 275-299 |
| 73X | 22 | | PA | | 10-0 | 21-66-11 | D05290J | | 15 | | | | | | 050-099, 162-199 |
| 73Y | 22 | | PA | | 4-0 | 21-66-21 | D05290J | | 6 | | | | | | 050-099, 162-199 |
| 740 | 20 | | PA | | 6-0 | 21-45-11 | D04340J | | 13 | | | | | | ALL |
| 741 | 20 | | PA | | 3-0 | 26-15-12 | D03730 | | C2 | | | | | | ALL |
| 742 | 22 | | PA | | 7-0 | 26-15-12 | D03730 | | C3 | | | | | | ALL |
| 743 | 24 | | PK | | 3-0 | 32-09-12 | D03730 | | X1 | | | | | | ALL |
| 744 | 24 | | PK | | 8-0 | 32-09-12 | D03730 | | X2 | | | | | | ALL |
| 745 | 20 | | PA | | 7-0 | 21-51-11 | D03696 | | 1 | | | | | | ALL |
| 746 | 24 | | PK | | 7-0 | 21-51-11 | D03696 | | 2 | | | | | | ALL |
| 747 | 24 | | PK | | 8-0 | 32-09-12 | D03696 | | 12 | | | | | | ALL |
| 748 | 24 | | PK | | 3-0 | 32-09-12 | D03696 | | 6 | | | | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 44

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 749 | 24 | | PK | 3-0 | 21-26-11 | K00346 | X1 | C | | | | | TB0192Z | 16 | BJ | | 050-099, 155-199, 276-299 |
| 749 | 24 | | PK | 3-0 | 21-26-11 | K00346 | X1 | C | | | | | TB0192Y | C007 | BJ | | 150-154, 275 |
| 74A | 18 | | PA | 5-0 | 21-66-21 | D05318J | 4 | DK | | | | | TB0320F | C007 | 2 | | 050-099, 162-199 |
| 74B | 18 | | PA | 5-0 | 21-66-21 | D05318J | 5 | DK | | | | | TB0320F | A008 | 2 | | 050-099, 162-199 |
| 74C | 18 | | PA | 5-0 | 21-66-21 | D05318J | 6 | DK | | | | | TB0320F | C008 | 2 | | 050-099, 162-199 |
| 74E | 20 | | PA | 4-0 | 21-66-21 | D05318J | 7 | | | | | | TB0210Y | A003 | BJ | | 050 |
| 74E | 20 | | PA | 4-0 | 21-66-21 | D05318J | 7 | | | | | | TB0210X | D003 | BJ | | 051-099 |
| 74E | 20 | | PA | 6-0 | 21-66-21 | D05318J | 7 | | | | | | TB0210X | D003 | BJ | | 162-199 |
| 74F | 20 | | PA | 6-0 | 21-66-21 | D05318J | 8 | | | | | | D13850 | A1 | | | 050-099, 162-199 |
| 74G | 20 | | PA | 12-0 | 21-66-21 | D05318J | 9 | | | | | | D13850 | B1 | | | 050-099, 162-199 |
| 74H | 22 | | PA | 6-0 | 21-66-21 | D05290J | 2 | | | | | | D13850 | X2 | | | 050-099, 162-199 |
| 74N | 22 | | PA | 5-0 | 21-66-21 | D05290J | 7 | | | | | | SP04072 | | W | | 050-099, 162-199 |
| 74R | 22 | | PA | 10-0 | 21-66-21 | D05290J | 8 | | | | | | TB0264D | A003 | 2 | | 050-099, 162-199 |
| 74X | 20 | | PA | 6-0 | 21-66-21 | SP04068 | | | W | | | | GDX0001 | D.. | 2 | | 050-099, 162-199 |
| 74Y | 20 | | PA | 6-0 | 21-66-21 | SP04070 | | | W | | | | GDX0001 | D.. | 2 | | 050-099, 162-199 |
| 751 | 24 | | PK | 7-0 | 21-53-22 | D03694 | 5 | | | | | | TB0192X | A004 | BJ | | ALL |
| 752 | 20 | | PA | 3-0 | 21-53-22 | D03694 | 4 | | | | | | GDX0007 | D.. | 2 | | ALL |
| 753 | 24 | | PK | 3-0 | 32-09-12 | D03694 | 6 | | | | | | TB0084Z | 9 | BJ | | ALL |
| 755 | 24 | | PK | 8-0 | 32-09-12 | D03694 | 12 | | | | | | TB0082Y | A002 | BJ | | ALL |
| 757 | 24 | | PK | 3-0 | 21-26-11 | D03788 | A1 | | | | | | TB0082Y | C001 | BJ | | ALL |
| 758 | 24 | | PK | 6-0 | 21-26-11 | D03788 | A2 | | | | | | TB0192Z | 16 | BJ | | 050-099, 155-199, 276-299 |
| 758 | 24 | | PK | 6-0 | 21-26-11 | D03788 | A2 | | | | | | TB0192Y | C007 | BJ | | 150-154, 275 |
| 759 | 24 | | PK | 3-0 | 21-26-11 | D03788 | X1 | | | | | | TB0082Y | C001 | BJ | | ALL |
| 75A | 22 | | PA | 7-0 | 21-66-21 | D13850 | X1 | | | | | | TB0320X | B005 | BJ | | 050-099, 162-199 |
| 75B | 20 | | PA | 7-0 | 21-66-21 | D13850 | A2 | | | | | | TB0320X | C005 | BJ | | 050-099, 162-199 |
| 75C | 20 | | PA | 7-0 | 21-66-21 | D13850 | B2 | | | | | | TB0320X | D005 | BJ | | 050-099, 162-199 |
| 75D | 18 | | PA | 5-0 | 21-66-41 | D05318J | 12 | DK | | | | | TB0320F | A007 | 2 | | 050-099, 150, 152-199 |
| 75E | 18 | | PA | 6-0 | 21-66-41 | D05318J | 13 | DK | | | | | TB0190F | C017 | 2 | | 050-099, 150, 152-199 |
| 75F | 18 | | PA | 6-0 | 21-66-41 | D05318J | 14 | DK | | | | | TB0192F | A003 | 2 | | 050-099, 150, 152-199 |
| 75G | 22 | | PA | 3-0 | 21-66-41 | D05318J | 11 | | | | | | D05290J | 10 | | | 050-099, 150, 152-199 |
| 75H | 22 | | PA | 6-0 | 21-66-41 | D05318J | 10 | | | | | | TB0190X | D004 | BJ | | 050-099, 150, 152-199 |
| 75I | 22 | | PA | 7-0 | 21-66-41 | D13854 | X2 | | | | | | TB0320Y | A010 | BJ | | 050-099, 150, 152-199 |
| 75J | 20 | | PA | 6-0 | 21-66-41 | D05318J | 16 | | | | | | D13854 | A1 | | | 050-099, 150, 152-199 |
| 75L | 20 | | PA | 12-0 | 21-66-41 | D05318J | 17 | | | | | | D13854 | B1 | | | 050-099, 150, 152-199 |
| 75M | 22 | | PA | 5-0 | 21-66-41 | D05318J | 18 | | | | | | SP04088 | | W | | 050-099, 150, 152-199 |
| 75N | 22 | | PA | 5-0 | 21-66-41 | D05318J | 19 | | | | | | TB0320Y | A010 | BJ | | 050-099, 150, 152-199 |
| 75Q | 22 | | PA | 3-0 | 21-66-41 | D05318J | 20 | | | | | | D05290J | 12 | | | 050-099, 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 45

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 75R | 22 | | PA | | 4-0 | 21-66-41 | D05290J | | | | | | | | 050-099, 150, 152-199 |
| 75U | 20 | | PA | | 6-0 | 21-66-41 | D05318J | | | | | | | | 050-099, 150, 152-199 |
| 75V | 20 | | PA | | 6-0 | 21-66-41 | SP04084 | | | | | | | | 050-099, 150, 152-199 |
| 75W | 20 | | PA | | 6-0 | 21-66-41 | SP04086 | | | | | | | | 050-099, 150, 152-199 |
| 760 | 20 | | PA | | 2-0 | 21-26-11 | D03788 | | | X2 | | | | | ALL |
| 761 | 24 | | PK | | 2-0 | 21-61-31 | TB0088D | | | A002 | | | | | ALL |
| 764 | 24 | | PK | | 9-0 | 21-51-21 | D05612J | | | 4 | | | | | ALL |
| 765 | 22 | | PA | | 6-0 | 21-61-11 | D06076J | | | 3 | | | | | ALL |
| 766 | 24 | | PK | | 5-0 | 21-51-21 | D05612J | | | 6 | | | | | ALL |
| 767 | 24 | | PK | | 5-0 | 21-51-21 | D05612J | | | 7 | | | | | ALL |
| 768 | 24 | | PK | | 5-0 | 21-51-21 | D05612J | | | 8 | | | | | ALL |
| 769 | 24 | | PK | | 5-0 | 21-51-21 | D05612J | | | 9 | | | | | 050-099 |
| 769 | 24 | | PK | | 5-0 | 21-51-21 | D05612J | | | 9 | | | | | 150-199, 275-299 |
| 76G | 22 | | PA | | 6-0 | 21-66-41 | D13854 | | | X1 | | | | | 050 |
| 76G | 22 | | PA | | 6-0 | 21-66-41 | D13854 | | | X1 | | | | | 051-099, 150, 152-199 |
| 76H | 20 | | PA | | 6-0 | 21-66-41 | D13854 | | | A2 | | | | | 050-099, 150, 152-199 |
| 76I | 20 | | PA | | 6-0 | 21-66-41 | D13854 | | | B2 | | | | | 050-099, 150, 152-199 |
| 772 | 22 | | PA | | 4-0 | 29-32-11 | D05612J | | | 31 | | | | | ALL |
| 778 | 20 | | PA | | 3-0 | 34-31-31 | D03698 | | | 11 | | | | | ALL |
| 779 | 24 | | PK | | 3-0 | 36-23-21 | D05768J | | | 26 | | | | | ALL |
| 780 | 24 | | PK | | 3-0 | 36-23-21 | D05768J | | | 27 | | | | | ALL |
| 781 | 24 | | PK | | 3-0 | 36-23-21 | D05768J | | | 9 | | | | | ALL |
| 782 | 24 | | PK | | 3-0 | 36-23-21 | D05768J | | | 29 | | | | | ALL |
| 783 | 24 | | PK | | 3-0 | 36-23-21 | D05768J | | | 28 | | | | | ALL |
| 785 | 20 | | PA | | 3-0 | 21-51-21 | D03694 | | | 7 | | | | | ALL |
| 786 | 22 | | PA | | 4-0 | 33-51-21 | D05592J | | | 11 | | | | | ALL |
| 787 | 22 | | PA | | 4-0 | 33-51-21 | D05592J | | | 10 | | | | | ALL |
| 788 | 22 | | PA | | 7-0 | 33-21-21 | D05660J | | | 9 | | | | | ALL |
| 789 | 24 | | PK | | 3-0 | 29-11-12 | D00616 | | | B2 | | | | | ALL |
| 78B | 20 | | PQ | HF | 8-0 | 78-34-21 | D05266J | | | 12 | | | | | ALL |
| 78BZ | | | | HF | 0-0 | 78-34-21 | D05266J | | | DED | | | | | ALL |
| 78C | 20 | | PQ | HN | 5-0 | 78-34-21 | D05266J | | | 13 | | | | | ALL |
| 78CZ | | | | HN | 0-0 | 78-34-21 | D05266J | | | 9 | | | | | ALL |
| 78E | 20 | | PQ | HK | 10-0 | 78-34-21 | D20104 | | | C2 | | | | | ALL |
| 78EZ | | | | HK | 0-0 | 78-34-21 | D20104 | | | DED | | | | | ALL |
| 78F | 20 | | UA | | 6-0 | 78-34-21 | TB0084Z | | | | | | | | ALL |
| 78G | 20 | | PA | | 6-0 | 78-34-21 | D03728 | | | C3 | | | | | ALL |
| 78H | 20 | | PQ | HP | 12-0 | 78-34-21 | D05326J | | | 23 | | | | | ALL |
| 78HZ | | | | HP | 0-0 | 78-34-21 | D05326J | | | | | | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 46

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 78K | 20 | | PA | | 5-0 | 78-34-21 | GDX0016 | S.. | 2 | | TB0084Z | | | HM | ALL |
| 78T | 24 | | PK | | 15-0 | 28-22-12 | K00330 | X2 | C | | TB0212Y | C006 | BJ | | 150-154, 275 |
| 78U | 24 | | PK | | 15-0 | 28-22-12 | K00330 | X1 | C | | TB0212Z | 17 | BJ | | ALL |
| 790 | 22 | | PA | | 6-0 | 29-11-12 | D00616 | A2 | | | TB0192Z | 17 | BJ | | ALL |
| 791 | 24 | | PK | | 3-0 | 29-11-12 | D00616 | X1 | | | TB0082Y | C004 | BJ | | ALL |
| 792 | 24 | | PK | | 2-0 | 29-11-12 | D00616 | B3 | | | D00618 | X1 | | | ALL |
| 793 | 22 | | PA | | 9-0 | 29-11-12 | D00616 | A3 | | | M00921 | A | C | | ALL |
| 794 | 24 | | PK | | 6-0 | 29-11-12 | D00616 | X2 | | | TB0274D | A020 | 2 | | ALL |
| 795 | 24 | | PK | | 8-0 | 29-11-12 | TB0082D | A012 | 2 | * | D05612J | 21 | | | ALL |
| 796 | 22 | | PA | | 10-0 | 29-11-12 | M00301 | A | C | | D00614 | A2 | | | ALL |
| 797 | 20 | | PA | | 6-0 | 23-32-11 | D05561J | 1 | | | TB0192Y | A015 | BJ | | ALL |
| 798 | 20 | | PA | | 6-0 | 23-32-11 | D05561J | 2 | | | TB0192Y | A015 | BJ | | 050-099, 150-199 |
| 799 | 20 | | PA | | 6-0 | 23-32-11 | D05561J | 3 | | | TB0192X | A018 | BJ | | 050-099, 150-199 |
| 79B | 24 | | PK | | 20-0 | 28-42-12 | D31186 | 2 | | | TB0212Y | A007 | BJ | | ALL |
| 79G | 24 | | PK | | 20-0 | 28-42-12 | D31184 | 3 | | | TB0212Y | A007 | BJ | | ALL |
| 79H | 24 | | PK | | 20-0 | 28-22-12 | D31186 | 4 | | | TB0082Y | A003 | BJ | | 050-099, 155-199, 276-299 |
| 79H | 24 | | PK | | 20-0 | 28-22-12 | D31186 | 4 | | | TB0212Y | C006 | BJ | | 150-154, 275 |
| 79J | 24 | | PK | | 20-0 | 28-22-12 | D31186 | 7 | | | TB0212Z | 17 | BJ | | ALL |
| 79Q | 24 | | PK | | 20-0 | 28-42-12 | D31186 | 3 | | | D31184 | 5 | | | ALL |
| 79T | 22 | | PA | | 10-0 | 73-21-19 | TB0274D | A036 | 2 | | TB0254Z | 8 | BJ | | 275-299 |
| 79U | 22 | | PA | | 3-0 | 73-21-19 | TB0274D | C036 | 2 | | TB0274D | C037 | 2 | | 275-299 |
| 79V | 24 | | PK | | 20-0 | 28-42-12 | D31184 | 2 | | | TB0212Z | 19 | BJ | | ALL |
| 79X | 24 | | PK | | 20-0 | 28-22-12 | D31184 | 7 | | | TB0212Z | 17 | BJ | | ALL |
| 800 | 20 | | PA | | 6-0 | 23-32-11 | D05561J | 4 | | | TB0192X | B018 | BJ | | 050-099, 150-199 |
| 801 | 22 | | PA | | 6-0 | 29-11-12 | D05612J | 24 | | | TB0192Z | 17 | BJ | | ALL |
| 803 | 24 | | PK | | 5-0 | 36-11-52 | TB0274Y | C011 | BJ | | D01724 | C1 | | | ALL |
| 804 | 22 | | PA | | 4-0 | 36-11-41 | TB0304Y | C012 | BJ | | D05688J | 7 | | | ALL |
| 805 | 24 | | PK | | 5-0 | 36-11-41 | D01724 | D1 | | | TB0192Y | A006 | BJ | | ALL |
| 807 | 24 | | PK | | 5-0 | 36-11-41 | D01724 | D2 | | | TB0190X | C013 | BJ | | ALL |
| 808 | 18 | | PA | | 4-0 | 36-11-52 | D05768J | 14 | DL | | SM00025 | 9 | | | 050-099, 155 |
| 808 | 18 | | PA | | 6-0 | 36-11-52 | D05768J | 14 | DL | | SM00025 | 9 | | | 150-154, 275 |
| 808 | 18 | | PA | | 5-0 | 36-11-52 | D05768J | 14 | DL | | SM00025 | 9 | | | 156, 162-166, 276 |
| 809 | 22 | | PA | | 4-0 | 36-11-52 | D05768J | 42 | | | SM00025 | 9 | | | 050-099 |
| 809 | 22 | | PA | | 5-0 | 36-11-52 | D05768J | 42 | | | SM00025 | 9 | | | 150-154, 156, 162-166 |
| 809 | 22 | | PA | | 7-0 | 36-11-52 | D05768J | 42 | | | SM00025 | 9 | | | 155 |
| 809 | 22 | | PA | | 7-0 | 36-11-52 | D05768J | 42 | | | TB0254Y | C004 | BJ | | 157, 167-199, 277-299 |
| 809 | 22 | | PA | | 6-0 | 36-11-52 | D05768J | 42 | | | SM00025 | 9 | | | 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 47

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | |
| 80D | 24 | | PK | 8-0 | 21-61-81 | D12208 | | X1 | | | TB0320Y | A034 | BJ | | 050-099, 151-199, 275-299 |
| 80E | 24 | | PK | 8-0 | 21-61-81 | D12208 | | X2 | | | TB0320D | A032 | 2 | | 050-099, 155-199, 275-299 |
| 80E | 24 | | PK | 8-0 | 21-61-81 | D12208 | | X2 | | | TB0320D | A032 | BJ | | 151-154 |
| 80F | 24 | | PK | 5-0 | 21-61-81 | D08680J | | 24 | | | TB0320D | C032 | 2 | | 050-099, 155-199, 275-299 |
| 80F | 24 | | PK | 5-0 | 21-61-81 | D08680J | | 24 | | | TB0320D | C032 | BJ | | 151-154 |
| 80G | 24 | | PK | 8-0 | 21-61-81 | D13438 | | X1 | | | TB0320Y | A034 | BJ | | 050-099, 151-199, 275-299 |
| 80H | 24 | | PK | 6-0 | 21-26-21 | D01006 | | B2 | | | D12240 | | 1 | | 050-099, 155-199, 276-299 |
| 80K | 24 | | PK | 4-0 | 21-26-21 | D12240 | | 3 | | | TB0190X | A003 | BJ | | 050-099, 155-199, 276-299 |
| 80L | 24 | | PK | 4-0 | 21-26-21 | D12240 | | 5 | | | TB0192X | C018 | BJ | | 050-099, 155-199, 276-299 |
| 80M | 24 | | PK | 4-0 | 21-26-11 | D12240 | | 6 | | | TB0192Z | | 16 | BJ | 050-099, 155-199, 276-299 |
| 80N | 24 | | PK | 8-0 | 21-26-11 | D12240 | | 12 | | | TB0088D | A015 | 2 | | 050-099, 155-199, 276-299 |
| 80R | 24 | | PK | 6-0 | 21-26-11 | D04646J | | 6 | | | D12240 | | 7 | | 050-099, 155-199 |
| 80R | 24 | | PK | 4-0 | 21-26-11 | D04646J | | 6 | | | D12240 | | 7 | | 276-299 |
| 80T | 24 | | PK | 4-0 | 21-26-11 | D12240 | | 11 | | | TB0190X | D013 | BJ | | 050-099, 155-199, 276-299 |
| 80U | 20 | | PA | 6-0 | 21-26-11 | K02092 | | 11 | C | | GDX0011 | D.. | F | * | 050-099, 155-199, 276-299 |
| 80V | 22 | | PA | 10-0 | 30-21-11 | D04340J | | 20 | | | D12128 | | 6 | | 050-099 |
| 80V | 22 | | PA | 12-0 | 30-21-11 | D04340J | | 20 | | | D12128 | | 6 | | 150-199 |
| 80W | 22 | | PA | 10-0 | 30-21-11 | D04340J | | 6 | | | D12128 | | 4 | | 050-099 |
| 80W | 22 | | PA | 12-0 | 30-21-11 | D04340J | | 6 | | | D12128 | | 4 | | 150-199 |
| 80X | 22 | | PA | 10-0 | 30-21-11 | D04340J | | 16 | | | D12128 | | 5 | | 050-099 |
| 80X | 22 | | PA | 12-0 | 30-21-11 | D04340J | | 16 | | | D12128 | | 5 | | 150-199 |
| 80Y | 22 | | PA | 8-0 | 30-21-11 | D05374J | | 7 | | | TB0254Z | | 8 | BJ | 050-099 |
| 80Y | 22 | | PA | 10-0 | 30-21-11 | D05374J | | 7 | | | TB0254Z | | 8 | BJ | 150-199 |
| 810 | 22 | | PA | 3-0 | 36-11-52 | D01724 | | X1 | | | SM00025 | | | | 050-099 |
| 810 | 22 | | PA | 5-0 | 36-11-52 | D01724 | | X1 | | | SM00025 | | | | 150-154, 162-165, 275-276 |
| 810 | 22 | | PA | 6-0 | 36-11-52 | D01724 | | X1 | | | SM00025 | | | | 155 |
| 810 | 22 | | PA | 4-0 | 36-11-52 | D01724 | | X1 | | | SM00025 | | | | 156, 166 |

WIRE LIST
D280T132

91-21-11
Section W0190
Page 48
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 810 | 22 | | PA | 4-0 | 36-11-52 | D01724 | | X1 | | | | | TB0254Y | C004 | BJ | | 157, 167-199, 277-299 |
| 811 | 22 | | PA | 6-0 | 36-11-52 | TB0274D | | C023 | 2 | | | | D05768J | 39 | | | ALL |
| 812 | 24 | | PK | 6-0 | 36-11-52 | TB0274Y | | C011 | BJ | | | | D05768J | 40 | | | ALL |
| 813 | 24 | | PK | 9-0 | 32-09-12 | D10478 | | X2 | | | | | TB0082Z | 7 | BJ | | ALL |
| 814 | 22 | | PA | 5-0 | 27-81-21 | D04962J | | | 34 | | | | TB0274Y | C003 | BJ | | ALL |
| 815 | 18 | | PA | 5-0 | 27-81-21 | D04962J | | | 33 | | | | TB0274G | 8 | 2 | | ALL |
| 816 | 20 | | PA | 3-0 | 33-44-11 | D05660J | | | 6 | | | | TB0304Y | C016 | BJ | | ALL |
| 817 | 22 | | PA | 2-0 | 30-21-11 | TB0254Z | | | 8 | BJ | | | TB0254D | A011 | 2 | | 050-099 |
| 817 | 22 | | PA | 3-0 | 30-21-11 | TB0254Z | | | 8 | BJ | | | TB0254D | A011 | 2 | | 150-199, 275-299 |
| 81F | 22 | | PA | 12-0 | 30-21-11 | D12128 | | | 7 | | | | TB0320Z | 22 | BJ | | 050-099, 150-199 |
| 81G | 22 | | PA | 12-0 | 30-21-11 | D12128 | | | 2 | | | | TB0320Z | 22 | BJ | | 050-099, 150-199 |
| 81J | 22 | | PA | 5-0 | 30-21-11 | D04340J | | | 19 | | | | TB0320Z | 22 | BJ | | 050-099 |
| 81J | 22 | | PA | 6-0 | 30-21-11 | D04340J | | | 19 | | | | TB0320Z | 22 | BJ | | 150-199 |
| 81K | 22 | | PA | 12-0 | 30-21-11 | D12136 | | | 7 | | | | TB0320Z | 22 | BJ | | 050-099, 150-199 |
| 81L | 22 | | PA | 10-0 | 30-21-11 | D04340J | | | 18 | | | | D12124 | 9 | | | 050-099 |
| 81L | 22 | | PA | 12-0 | 30-21-11 | D04340J | | | 18 | | | | D12124 | 9 | | | 150-199 |
| 81N | 22 | | PA | 10-0 | 30-21-11 | D04340J | | | 17 | | | | D12124 | 10 | | | 050-099 |
| 81N | 22 | | PA | 12-0 | 30-21-11 | D04340J | | | 17 | | | | D12124 | 10 | | | 150-199 |
| 81P | 22 | | PA | 13-0 | 30-21-11 | D12128 | | | 3 | | | | TB0254Y | C005 | BJ | | 050-099 |
| 81P | 22 | | PA | 10-0 | 30-21-11 | D12128 | | | 3 | | | | TB0254Y | C005 | BJ | | 150-199 |
| 81R | 22 | | PA | 13-0 | 30-21-11 | D12136 | | | 5 | | | | TB0254Y | C005 | BJ | | 050-099 |
| 81R | 22 | | PA | 10-0 | 30-21-11 | D12136 | | | 5 | | | | TB0254Y | C005 | BJ | | 150-199 |
| 81T | 20 | | PA | 10-0 | 30-21-11 | D12136 | | | 2 | | | | GDX0001 | D.. | 2 | | 050-099, 150-154 |
| 81T | 20 | | PA | 10-0 | 30-21-11 | D12136 | | | 2 | | | | GDX0001 | D.. | 2 | * | 155-199 |
| 81U | 20 | | PA | 10-0 | 30-21-11 | D12136 | | | 6 | | | | GDX0001 | D.. | 2 | | 050-099, 150-154 |
| 81U | 20 | | PA | 10-0 | 30-21-11 | D12136 | | | 6 | | | | GDX0001 | D.. | 2 | * | 155-199 |
| 81W | 22 | | PA | 11-0 | 30-21-11 | D12136 | | | 3 | | | | D05290J | 5 | | | 050-099 |
| 81W | 24 | | PK | 12-0 | 30-21-11 | D05290J | | | 5 | | | | D12136 | 3 | | | 150-199 |
| 81X | 22 | | PA | 14-0 | 30-21-11 | D12136 | | | 1 | | | | TB0320X | A001 | BJ | | 050-099 |
| 81X | 24 | | PK | 14-0 | 30-21-11 | D12136 | | | 1 | | | | TB0320X | A001 | BJ | | 150-199 |
| 81Y | 20 | | PA | 12-0 | 30-21-11 | D12132 | | | 8 | | | | GDX0013 | D.. | 2 | | 050-099 |
| 81Y | 20 | | PA | 10-0 | 30-21-11 | D12132 | | | 8 | | | | GDX0013 | D.. | 2 | | 150-199 |
| 820 | 20 | | PA | 9-0 | 30-71-11 | D03730 | | | D3 | | | | D05688J | 10 | | | ALL |
| 821 | 18 | | PA | 9-0 | 30-71-11 | D03730 | | | D1 | | | | D05688J | 9 | DK | | ALL |
| 822 | 18 | | PA | 7-0 | 30-71-11 | D03730 | | | D2 | | | | TB0192G | 20 | 2 | | ALL |
| 823 | 18 | | PA | 6-0 | 30-71-11 | D05688J | | | 1 | DK | | | TB0192G | 20 | 2 | | ALL |
| 826 | 20 | | PA | 6-0 | 33-42-11 | D04340J | | | 25 | | | | TB0192Y | C015 | BJ | | ALL |
| 827 | 18 | | PA | 8-0 | 33-42-11 | D04340J | | | 24 | DK | | | K00162 | A2 | E | | 050-099 |
| 827 | 16 | | PA | 8-0 | 33-42-11 | D04340J | | | 24 | FM | | | K00162 | A2 | E | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 49

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 828 | 20 | | PA | 8-0 | 33-42-11 | D04346J | | 15 | | | | | K00162 | A3 | E | | 050-099 |
| 828 | 16 | | PA | 8-0 | 33-42-11 | D04346J | | 15 | FM | | | | K00162 | A3 | E | | 150-199, 275-299 |
| 829 | 18 | | PA | 8-0 | 33-42-11 | D04346J | | 21 | DK | | | | K00162 | A1 | E | | 050-099 |
| 829 | 16 | | PA | 8-0 | 33-42-11 | D04346J | | 21 | FM | | | | K00162 | A1 | E | | 150-199, 275-299 |
| 82A | 22 | | PA | 4-0 | 30-21-11 | D12132 | | 3 | | | | | D12124 | | | | 050-099 |
| 82A | 22 | | PA | 6-0 | 30-21-11 | D12124 | | 1 | | | | | D12132 | | | | 150-154 |
| 82A | 22 | | PA | 4-0 | 30-21-11 | D12124 | | 1 | | | | | D12132 | | | | 155-199 |
| 82D | 22 | | PA | 4-0 | 30-21-11 | D12132 | | 7 | | | | | D12124 | | | | 050-099 |
| 82D | 22 | | PA | 6-0 | 30-21-11 | D12124 | | 11 | | | | | D12132 | | | | 150-154 |
| 82D | 22 | | PA | 4-0 | 30-21-11 | D12124 | | 11 | | | | | D12132 | | | | 155-199 |
| 82E | 24 | | PK | 8-0 | 30-21-11 | D04004J | | 8 | | | | | TB0254Y | C005 | BJ | | 050-099 |
| 82E | 24 | | PK | 12-0 | 30-21-11 | D04004J | | 8 | | | | | TB0254Y | C005 | BJ | | 150-154 |
| 82E | 24 | | PK | 7-0 | 30-21-11 | D04004J | | 8 | | | | | TB0254Y | C005 | BJ | | 155-199 |
| 82F | 22 | | PA | 14-0 | 30-21-11 | D12128 | | 1 | | | | | TB0254Z | 8 | BJ | | 050-099 |
| 82F | 22 | | PA | 10-0 | 30-21-11 | D12128 | | 1 | | | | | TB0254Z | 8 | BJ | | 150-199 |
| 82H | 24 | | PK | 12-0 | 73-21-16 | D05612J | | 15 | | | | | D12124 | | | | 050-099, 150-199 |
| 82J | 20 | | PA | 12-0 | 73-21-16 | D12124 | | 5 | | | | | GDX0013 | D.. | 2 | | 050-099 |
| 82J | 20 | | PA | 10-0 | 73-21-16 | D12124 | | 5 | | | | | GDX0013 | D.. | 2 | | 150-199 |
| 82K | 20 | | PA | 10-0 | 30-81-11 | D03688 | | 4 | | | | | D05352J | | | | 050-099, 150-199 |
| 82M | 20 | | PA | 4-0 | 30-81-11 | D03688 | | 5 | | | | | GDX0015 | D.. | 2 | | 050-099, 150-199 |
| 82Y | 20 | | PA | 5-0 | 30-71-24 | D03748 | | | X1 | | | | TB0210Z | 11 | BJ | | 050-099 |
| 830 | 20 | | PA | 6-0 | 33-42-11 | TB0192Y | | | C015 | BJ | | | K00162 | X1 | C | | ALL |
| 831 | 20 | | PA | 6-0 | 33-42-11 | TB0274Y | | | A010 | BJ | | | K00162 | X2 | C | | ALL |
| 832 | 22 | | PA | 6-0 | 29-11-12 | M00925 | | | B | C | | | D04962J | 18 | | | ALL |
| 833 | 24 | | PK | 9-0 | 32-09-12 | D10478 | | | X1 | | | | TB0084Y | A008 | BJ | | ALL |
| 834 | 22 | | PA | 3-0 | 29-11-12 | D00614 | | | C1 | | | | TB0082Y | A005 | BJ | | ALL |
| 835 | 24 | | PK | 1-0 | 32-09-12 | TB0084Y | | | A008 | BJ | | | TB0084Z | 9 | BJ | | ALL |
| 836 | 24 | | PK | 2-0 | 29-11-12 | TB0274D | | | C020 | 2 | | | TB0212Y | C010 | BJ | | ALL |
| 837 | 22 | | PA | 3-0 | 29-11-12 | TB0192Z | | | | BJ | | | TB0274D | C018 | 2 | | ALL |
| 838 | 24 | | PK | 6-0 | 32-09-12 | D13021 | | | X1 | | | | TB0084Y | A008 | BJ | | 050-099 |
| 838 | 24 | | PK | 7-0 | 32-09-12 | D13021 | | | X1 | | | | TB0084Y | A008 | BJ | | 150-199, 275-299 |
| 839 | 24 | | PK | 3-0 | 32-09-12 | D13021 | | | X2 | | | | TB0082Y | C006 | BJ | | ALL |
| 83A | 20 | | PA | 5-0 | 30-71-24 | D03748 | | | X2 | | | | D05688J | 16 | | | 050-099 |
| 83B | 20 | | PA | 5-0 | 30-71-24 | D03748 | | | A1 | | | | TB0210Y | A001 | BJ | | 050-099 |
| 83D | 24 | | PK | 12-0 | 73-21-18 | D12248 | | | 7 | | | | TB0320Y | A020 | BJ | | 050-099, 150-199, 275-276 |
| 83D | 24 | | PK | 10-0 | 73-21-18 | D12248 | | | 7 | | | | TB0320Y | A020 | BJ | | 277-299 |
| 83E | 24 | | PK | 10-0 | 73-21-18 | D04646J | | | 43 | | | | D12248 | 3 | | | 050-099 |
| 83E | 24 | | PK | 10-0 | 73-21-18 | D12248 | | | 3 | | | | D04646J | 43 | | | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0190
Page 50
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | |
| 83F | 24 | | PK | 4-0 | 73-21-18 | D04646J | | 10 | | | | TB0320Y | A020 | BJ | | 050-099, 150-154, 275-276 |
| 83F | 24 | | PK | 5-0 | 73-21-18 | D04646J | | 10 | | | | TB0320Y | A020 | BJ | | 155-199, 277-299 |
| 83G | 22 | | PA | 4-0 | 30-81-11 | D05290J | | 3 | | | | TB0320Y | A012 | BJ | | 050-099, 155-199 |
| 83G | 22 | | PA | 6-0 | 30-81-11 | D05290J | | 3 | | | | TB0320Y | A012 | BJ | | 150-154 |
| 83H | 22 | | PA | 11-0 | 30-21-11 | D12124 | | 13 | | | | TB0320Y | A012 | BJ | | 050-099, 150-199 |
| 83J | 22 | | PA | 10-0 | 30-21-11 | D05612J | | 13 | | | | D12132 | 6 | | | 050-099, 150-199 |
| 83K | 20 | | PA | 5-0 | SPARE | D05266J | | 19 | | | | TB0320X | C006 | BJ | | 280-299 |
| 83N | 24 | | PK | 12-0 | 78-36-21 | D03704 | | B1 | | | | D03670 | A1 | | | ALL |
| 83P | 24 | | PK | 8-0 | 78-36-21 | D03670 | | A3 | | | | TB0254Y | A003 | BJ | | ALL |
| 83S | 20 | | PA | 5-0 | 78-34-21 | D03704 | | A3 | | | | GD00016 | D.. | 2 | | ALL |
| 840 | 22 | | PA | 12-0 | 30-21-11 | D12124 | | 2 | | | | D05326J | 19 | | | 050-099, 150-199 |
| 840 | 22 | | PA | 4-0 | 30-21-11 | D04340J | | 5 | | | | D05326J | 19 | | | 275-299 |
| 841 | 22 | | PA | 5-0 | 30-21-11 | D05326J | | 21 | | | | TB0320Y | A012 | BJ | | 050-099, 155-199 |
| 841 | 22 | | PA | 6-0 | 30-21-11 | D05326J | | 21 | | | | TB0320Y | A012 | BJ | | 150-154 |
| 841 | 22 | | PA | 4-0 | 30-21-11 | D04340J | | 6 | | | | D05326J | 21 | | | 275-299 |
| 842 | 24 | | PK | 7-0 | 30-21-11 | D04340J | | 7 | | | | TB0254Z | 8 | BJ | | ALL |
| 843 | 24 | | PK | 4-0 | 30-21-11 | D05374J | | 36 | | | | D05326J | 22 | | | ALL |
| 844 | 22 | | PA | 6-0 | 78-36-21 | D05326J | | 5 | | | | TB0274G | 9 | 2 | | 050-099 |
| 844 | 22 | | PA | 6-0 | 78-36-21 | TB0274G | | 9 | 2 | | | D05326J | 5 | | | 150-199, 275-299 |
| 844R | 20 | | PH | 3-0 | 26-23-12 | D13021 | | C2 | | | | TB0262Y | A003 | BJ | | 150-199, 275-299 |
| 845 | 22 | | PA | 8-0 | 78-36-21 | D13042 | | A2 | | | | D06584J | 5 | | | 050-099 |
| 845 | 22 | | PA | 9-0 | 78-36-21 | D13042 | | A2 | | | | D06584J | 5 | | | 150-199, 275-299 |
| 845R | 20 | | PH | 3-0 | 26-23-12 | D13021 | | B2 | | | | TB0262Y | C003 | BJ | | 150-199, 275-299 |
| 846 | 22 | | PA | 8-0 | 78-36-21 | D13042 | | B2 | | | | D06584J | 6 | | | 050-099 |
| 846 | 22 | | PA | 9-0 | 78-36-21 | D13042 | | B2 | | | | D06584J | 6 | | | 150-199, 275-299 |
| 846R | 20 | | PH | 3-0 | 26-23-12 | D13021 | | C1 | | | | TB0262Y | C004 | BJ | | 150-154 |
| 846R | 20 | | PH | 3-0 | 26-23-12 | D13021 | | C1 | | | | TB0262Z | 5 | BJ | | 155-199, 275-299 |
| 847 | 22 | | PA | 5-0 | 78-36-21 | D13042 | | A3 | | | | TB0274G | 9 | 2 | | 050-099 |
| 847 | 22 | | PA | 7-0 | 78-36-21 | D13042 | | A3 | | | | TB0274G | 9 | 2 | | 150-199, 275-299 |
| 847R | 20 | | PH | 3-0 | 26-23-12 | D13021 | | B1 | | | | TB0262Y | A005 | BJ | | 150-154 |
| 847R | 20 | | PH | 3-0 | 26-23-12 | D13021 | | B1 | | | | TB0262Z | 8 | BJ | | 155-199, 275-299 |
| 848 | 20 | | PA | 2-0 | 78-36-21 | D13042 | | A1 | | | | GD00005 | D.. | 2 | | 050-099 |
| 848 | 20 | | PA | 3-0 | 78-36-21 | D13042 | | A1 | | | | GD00005 | D.. | 2 | | 150-199, 275-299 |
| 849 | 24 | | PK | 1-0 | 32-09-12 | TB0082Y | | C006 | BJ | | | TB0082Z | 7 | BJ | | 050-099 |
| 849 | 24 | | PK | 1-0 | 32-09-12 | TB0082Z | | 7 | BJ | | | TB0082Y | C006 | BJ | | 150-199, 275-299 |
| 84S | 20 | | PA | 8-0 | 78-34-21 | D03704 | | A1 | | | | TB0274Y | A004 | BJ | | ALL |
| 84X | 20 | | PA | 12-0 | 78-34-21 | D03704 | | A2 | | | | D04284J | 30 | | | ALL |
| 850 | 22 | | PA | 5-0 | 78-36-21 | D13042 | | B1 | | | | TB0274G | 9 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 51

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 850 | 22 | PA | | 7-0 | 78-36-21 | D13042 | | B1 | | | | | TB0274G | 9 | 2 | | 150-199, 275-299 |
| 851 | 22 | PA | | 5-0 | 78-36-21 | D13042 | | X1 | | | | | TB0274G | 9 | 2 | | 050-099 |
| 851 | 22 | PA | | 7-0 | 78-36-21 | D13042 | | X1 | | | | | TB0274G | 9 | 2 | | 150-199, 275-299 |
| 852 | 22 | PA | | 5-0 | 78-36-21 | D13042 | | X2 | | | | | TB0274X | D012 | BJ | | 050-099 |
| 852 | 22 | PA | | 7-0 | 78-36-21 | D13042 | | X2 | | | | | TB0274X | D012 | BJ | | 150-199, 275-299 |
| 853 | 22 | PA | | 6-0 | 78-36-21 | TB0274X | | A013 | BJ | | | | D06584J | 1 | | | ALL |
| 854 | 20 | UA | | 3-0 | 32-42-11 | D00666 | | | | AA | | | GD00001 | S.. | 2 | | ALL |
| 855 | 24 | PK | | 5-0 | 32-42-11 | D00666 | | X2 | | | | | D05435J | 43 | | | ALL |
| 856 | 24 | PK | | 5-0 | 32-42-11 | D00666 | | X1 | | | | | D05768J | 45 | | | ALL |
| 857 | 22 | PQ | V7 | 6-0 | 78-36-21 | D05326J | | 9 | | | | | TB0274X | D012 | BJ | | 050-099 |
| 857 | 22 | PQ | DC | 6-0 | 78-36-21 | D05326J | | 9 | | | | | TB0274X | D012 | BJ | | 150-199, 275-299 |
| 857Z | | | V7 | 0-0 | 78-36-21 | D05326J | | | | | V7 | | TB0274X | DED | | | 050-099 |
| 857Z | | | DC | 0-0 | 78-36-21 | D05326J | | | | | \$ | F2 | TB0274X | DED | | | 150-199, 275-299 |
| 858 | 20 | PA | | 2-0 | 78-36-21 | D13042 | | B3 | | | | | GD00005 | D.. | 2 | | 050-099 |
| 858 | 20 | UA | | 3-0 | 78-36-21 | D13042 | | B3 | | | | | GD00005 | D.. | 2 | | 150-199 |
| 858 | 20 | PA | | 3-0 | 78-36-21 | D13042 | | B3 | | | | | GD00005 | D.. | 2 | | 275-299 |
| 859 | 20 | UA | | 8-0 | 78-36-21 | D05326J | | | | | V7 | | GD00005 | S.. | 2 | | 050-099 |
| 859 | 20 | UA | | 9-0 | 78-36-21 | D05326J | | | | \$ | F2 | | GD00005 | S.. | 2 | | 150-199, 275-299 |
| 85F | 20 | PA | | 12-0 | 78-36-21 | D20100 | | D1 | | | | | GD00009 | D.. | 2 | | ALL |
| 85G | 20 | PA | | 12-0 | 78-36-21 | D20100 | | B1 | | | | | GD00009 | D.. | 2 | | ALL |
| 85K | 22 | PA | | 8-0 | 78-36-21 | D05068J | | 56 | | | | | TB0274D | C015 | 2 | | ALL |
| 85L | 22 | PA | | 8-0 | 78-36-21 | D10478 | | B3 | | | | | D05068J | 54 | | | ALL |
| 85M | 22 | PA | | 8-0 | 78-36-21 | D10478 | | B2 | | | | | D05068J | 55 | | | ALL |
| 85N | 22 | PA | | 10-0 | 78-36-21 | D20100 | | D2 | | | | | D05068J | 58 | | | ALL |
| 85P | 22 | PA | | 10-0 | 78-36-21 | D20100 | | B2 | | | | | D05068J | 57 | | | ALL |
| 85S | 24 | PK | | 10-0 | 78-36-21 | D03704 | | X2 | | | | | D04962J | 7 | | | 050-099 |
| 85S | 24 | PK | | 8-0 | 78-36-21 | D03704 | | X2 | | | | | D04962J | 7 | | | 150-199, 275-299 |
| 871 | 20 | PA | | 6-0 | 21-26-11 | SP01618 | | | | W | | | GD00009 | D.. | 2 | | ALL |
| 876 | 22 | PA | | 3-0 | 29-11-12 | D00616 | | A1 | | | | | TB0082Y | A005 | BJ | | ALL |
| 877 | 24 | PK | | 6-0 | 21-61-31 | D04646J | | 55 | | | | | D10154 | 3 | | | ALL |
| 878 | 24 | PK | | 8-0 | 21-61-31 | D04646J | | 56 | | | | | D03754 | C1 | | | ALL |
| 87B | 20 | PA | | 8-0 | 78-34-21 | D04284J | | 29 | | | | | TB0274Y | A003 | BJ | | ALL |
| 87E | 24 | PK | | 10-0 | 78-36-21 | D03704 | | X1 | | | | | D05068J | 51 | | | ALL |
| 87F | 24 | PK | | 10-0 | 78-36-21 | D03704 | | B2 | | | | | D05068J | 46 | | | ALL |
| 87G | 20 | PA | | 5-0 | 78-36-21 | D03670 | | C1 | | | | | GD00016 | D.. | 2 | | ALL |
| 87H | 22 | PA | | 10-0 | 78-36-21 | D03670 | | C2 | | | | | D05068J | 60 | | | ALL |
| 881 | 24 | PK | | 8-0 | 21-61-31 | D04646J | | 59 | | | | | D03754 | D3 | | | ALL |
| 882 | 22 | PA | | 5-0 | 21-61-31 | D04646J | | 60 | | | | | TB0212Z | 15 | BJ | | ALL |
| 883 | 24 | PK | | 8-0 | 21-61-31 | D04646J | | 61 | | | | | D03754 | D2 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0190
Page 52
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|-------|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 884 | 24 | | PK | 5-0 | 21-26-11 | D04646J | | 51 | | | | | SP01616 | | W | | ALL |
| 885 | 22 | | PA | 8-0 | 29-11-12 | D05612J | | 22 | | | | | D00614 | | C2 | | ALL |
| 886 | 24 | | PK | 8-0 | 29-11-12 | D05612J | | 11 | | | | | TB0082Z | | 14 BJ | | ALL |
| 889 | 22 | | PA | 7-0 | 29-11-12 | M00921 | | B | C | | | | TB0274D | | A025 2 | | ALL |
| 88X | 22 | | PA | 10-0 | 73-21-19 | D20544 | | 1 | | | | | TB0274Y | | A029 BJ | | 050-099, 150-199 |
| 88Y | 20 | | PA | 10-0 | 73-21-19 | D20544 | | 12 | | | | | GD00017 | | D.. 2 | | 050-099, 150-199 |
| 890 | 24 | | PK | 3-0 | 21-58-15 | TB0212Y | | A012 | BJ | | | | K00345 | | X1 C | | ALL |
| 892 | 22 | | PA | 6-0 | 27-09-13 | D05317J | | 1 | | | | | TB0274D | | C026 2 | | ALL |
| 893 | 22 | | PA | 6-0 | 27-09-13 | D05317J | | 5 | | | | | TB0274D | | C025 2 | | ALL |
| 894 | 18 | | PA | 4-0 | 33-44-21 | D04962J | | 22 | | | | | TB0304G | | 31 2 | | ALL |
| 895 | 20 | | PA | 5-0 | 30-71-24 | D03748 | | A2 | | | | | TB0210Z | | 11 BJ | | 050-099 |
| 895 | 20 | | PA | 6-0 | 30-71-24 | TB0210Z | | 11 | BJ | | | | D03748 | | A2 | | 150-199 |
| 897 | 22 | | PA | 6-0 | 36-11-52 | TB0274D | | A023 | 2 | | | | D01724 | | X2 | | ALL |
| 898 | 20 | | PA | 3-0 | 32-09-12 | D03696 | | 11 | | | | | GD00007 | | D.. 2 | | ALL |
| 89A | 24 | | PK | 5-0 | 21-58-15 | TB0212Y | | A012 | BJ | | | | D06076J | | 6 | | ALL |
| 89C | 22 | | PA | 10-0 | 73-21-19 | D05328J | | 3 | | | | | D20544 | | 6 | | 050-099, 150-199 |
| 89C | 22 | | PA | 10-0 | 74-31-21 | D05328J | | 3 | | | | | TB0274D | | A037 2 | | 275-299 |
| 901B | 24 | | PW AQ | 0-0 | 34-53-21 | D05499J | | 13 | | | | | TB0274Y | | C039 BJ | | 275-299 |
| 901R | 24 | | PW AQ | 5-0 | 34-53-21 | D05499J | | 12 | | | | | TB0274Y | | A039 BJ | | 275-299 |
| 901Z | | | | 0-0 | 34-53-21 | D05499J | | 14 | | | | | TB0274Y | | A040 BJ | | 275-299 |
| 903 | 12 | | PA | 5-0 | 24-54-21 | C09000 | | 2 | D | | | | C00666 | | 2 D | | 150, 152-157 |
| 909 | 20 | | PA | 6-0 | 30-71-24 | TB0210Z | | 11 | BJ | | | | D03748 | | X1 | | 150-199 |
| 90A | 20 | | PA | 4-0 | 34-22-26 | D03684 | | 1 | | | | | GD00014 | | S.. 2 | | ALL |
| 90B | 22 | | PA | 9-0 | 34-22-26 | D05437J | | 4 | | | | | D03684 | | 2 | | 050-099 |
| 90B | 22 | | PA | 8-0 | 34-22-26 | D05437J | | 4 | | | | | D03684 | | 2 | | 150-199, 275-299 |
| 910 | 20 | | PA | 6-0 | 30-71-24 | TB0210X | | C010 | BJ | | | | D03748 | | X2 | | 150-199 |
| 91D | 24 | | PV BV | 3-0 | 73-21-14 | D05316J | | 1 | | | | | D06584J | | 2 | | 050-099 |
| 91D | 24 | | PV DK | 5-0 | 73-21-14 | D05316J | | 1 | | | | | D06584J | | 2 | | 150-199, 275-299 |
| 91DZ | | | | 0-0 | 73-21-14 | D05316J | | | | | | | D06584J | | | | 050-099 |
| 91DZ | | | | 0-0 | 73-21-14 | D05316J | | | | | | | D06584J | | | | 150-199, 275-299 |
| 91F | 16 | | PQ ME | 3-0 | 73-21-20 | D06260J | | 9 | FM | | | | D06584J | | 7 FM | | 050-099 |
| 91F | 16 | | PQ DE | 5-0 | 73-21-20 | D06260J | | 9 | FM | | | | D06584J | | 7 FM | | 150-199, 275-299 |
| 91FZ | | | | 0-0 | 73-21-20 | D06260J | | | | | | | D06584J | | | | 050-099 |
| 91FZ | | | | 0-0 | 73-21-20 | D06260J | | | | | | | D06584J | | | | 150-199 |
| 91FZ | | | | 0-0 | 73-21-20 | D06260J | | 29 | | | | | D06584J | | | | 275-276 |
| 91FZ | | | | 0-0 | 73-21-20 | D06260J | | | | | | | D06584J | | | | 277-299 |
| 91G | 24 | | PV BH | 3-0 | 73-21-11 | D05316J | | 29 | | | | | D05612J | | 18 | | 050-099 |
| 91G | 24 | | PV AU | 5-0 | 73-21-11 | D05316J | | 29 | | | | | D05612J | | 32 | | 150-199, 275-276 |
| 91G | 24 | | PV AU | 5-0 | 73-21-11 | D05316J | | 29 | | | | | D05612J | | 18 | | 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 53

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|---------|---------|------|--------|-----------------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0192 | 286T0192 | | | P37-R2-INTEGRATION (continued) | | | | | | | | | | | | |
| 91GZ | | | | BH | 0-0 | 73-21-11 | D05316J | | 34 | | D05612J | | 19 | | 050-099 | |
| 91GZ | | | | AU | 0-0 | 73-21-11 | D05316J | | 34 | | D05612J | | 33 | | 150-199, 275-276 | |
| 91GZ | | | | AU | 0-0 | 73-21-11 | D05316J | | 34 | | D05612J | | 19 | | 277-299 | |
| 91L | 24 | | PK | | 6-0 | 76-11-11 | D11756 | | Y1 | | TB0274Y | C004 | BJ | | 050-099 | |
| 91L | 22 | | PA | | 8-0 | 76-11-11 | D11756 | | Y1 | | TB0304Y | C019 | BJ | | 150-199 | |
| 91L | 22 | | PA | | 8-0 | 76-11-11 | D11756 | | Y1 | | TB0274Y | C004 | BJ | | 275-299 | |
| A-A | | | | | 0-0 | 23-25-21 | TS0193 | | 5 | | SP01600 | | W | | 050-099 | |
| A-A | | | | | 0-0 | 21-25-21 | TS0193 | | 5 | | SP01600 | | W | | 150-199, 275-299 | |
| A-B | | | | | 0-0 | 21-25-21 | TS0193 | | 4 | | SP01602 | | W | | ALL | |
| A-E | | | | | 0-0 | 21-58-15 | TS0230 | | 1 | | SP01612 | | W | | ALL | |
| A-F | | | | | 0-0 | 21-58-15 | TS0230 | | 2 | | SP01614 | | W | | ALL | |
| A-G | | | | | 0-0 | 21-26-11 | TS0245 | | 1 | | SP01616 | | W | | ALL | |
| A-H | | | | | 0-0 | 21-26-11 | TS0245 | | 2 | | SP01618 | | W | | ALL | |
| A-I | | | | | 0-0 | 21-66-21 | TS0525 | | 1 | | SP04066 | | W | | 050-099, 162-199 | |
| A-J | | | | | 0-0 | 21-25-21 | TS0193 | | 1 | | SP02252 | | W | | ALL | |
| A-K | | | | | 0-0 | 21-25-21 | TS0193 | | 3 | | SP02250 | | W | | ALL | |
| A-L | | | | | 0-0 | 21-25-21 | TS0193 | | 2 | | SP02254 | | W | | ALL | |
| A-O | | | | | 0-0 | 21-66-21 | TS0525 | | 2 | | SP04068 | | W | | 050-099, 162-199 | |
| A-P | | | | | 0-0 | 21-66-21 | TS0525 | | 4 | | SP04070 | | W | | 050-099, 162-199 | |
| A-Q | | | | | 0-0 | 21-66-21 | TS0525 | | 5 | | SP04072 | | W | | 050-099, 162-199 | |
| A-R | | | | | 0-0 | 21-66-21 | TS0525 | | 3 | | TS0525 | CAP | Y | | 050-099, 162-199 | |
| A-S | | | | | 0-0 | 21-66-41 | TS0527 | | 1 | | SP04082 | | W | | 050-099, 150, 152-199 | |
| A-T | | | | | 0-0 | 21-66-41 | TS0527 | | 2 | | SP04084 | | W | | 050-099, 150, 152-199 | |
| A-U | | | | | 0-0 | 21-66-41 | TS0527 | | 4 | | SP04086 | | W | | 050-099, 150, 152-199 | |
| A-V | | | | | 0-0 | 21-66-41 | TS0527 | | 5 | | SP04088 | | W | | 050-099, 150, 152-199 | |
| A-W | | | | | 0-0 | 21-66-41 | TS0527 | | 3 | | TS0527 | CAP | Y | | 050-099, 150, 152-199 | |
| FR1 | | | | | 0-0 | 73-21-14 | D06584J | | | F1 | D06584J | | 29 | | 150-199, 275-299 | |
| FR2 | | | | | 0-0 | 78-36-21 | D05326J | | | \$ | F2 | D05326J | | 7 | | 150-199, 275-299 |
| FRA | | | | | 0-0 | 73-21-14 | D06584J | | 29 | | D06584J | | | FJ | 050-099 | |
| FRB | | | | | 0-0 | 78-36-21 | D05326J | | | | V7 | D05326J | | 7 | | 050-099 |
| FRC | | | | | 0-0 | 78-34-11 | D04284J | | | | HC | D04284J | | 22 | | ALL |
| FRH | | | | | 0-0 | 73-21-14 | D05316J | | | | FH | D05316J | | 24 | | 050-099 |
| FRI | | | | | 0-0 | 78-34-21 | D05326J | | | | HI | D05326J | | 54 | | ALL |
| FRS | | | | | 0-0 | 73-21-11 | D06260J | | 29 | | D06260J | | | FS | 050-099 | |
| FRS | | | | | 0-0 | 73-21-11 | D06260J | | | | FS | D06260J | | 29 | | 150-199, 277-299 |
| FRW | | | | | 0-0 | 73-21-14 | D06584J | | 12 | | D06584J | | | FW | 050-099 | |
| FRW | | | | | 0-0 | 73-21-14 | D06584J | | | | FW | D06584J | | 12 | | 150-199, 275-299 |
| FRY | | | | | 0-0 | 73-21-14 | D05316J | | | | FY | D05316J | | 24 | | 150-199, 275-299 |
| PA1 | | | | | 0-0 | 99-99-99 | D10158 | | G2 | | D10158 | | G3 | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W0190
Page 54
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|-------|---------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0198 | 286T0198 | | | P37-S2-RIGHT MISC ELEC EQUIP PNL INTEG | | | | | | | | | | | | | |
| 001 | 22 | | PA | 6-9 | 28-25-21 | D03708 | | B2 | | | | | D04948J | 7 | | | 050-099 |
| 001 | 20 | | PA | 6-9 | 28-25-21 | D03708 | | B2 | | | | | D04948J | 7 | | | 150-199, 275-299 |
| 003 | 22 | | PA | 1-9 | 49-61-11 | D03708 | | A3 | | | | | D03744 | 8 | | | ALL |
| 004 | 22 | | PA | 6-11 | 49-61-11 | D03708 | | A1 | | | | | D04056J | 5 | | | ALL |
| 005 | 22 | | PA | 4-10 | 49-61-11 | D03708 | | A2 | | | | | TB0212Z | 18 | BJ | | ALL |
| 006 | 22 | | PA | 4-10 | 49-61-11 | D03708 | | X2 | | | | | TB0212Z | 18 | BJ | | ALL |
| 007 | 22 | | PA | 6-4 | 49-61-11 | D03744 | | 2 | | | | | D04056J | 2 | | | ALL |
| 008 | 22 | | PA | 1-9 | 49-61-11 | D03744 | | 4 | | | | | D03708 | X1 | | | ALL |
| 009 | 22 | | PA | 6-0 | 49-61-11 | TB0274D | | C022 | 2 | | | | D04056J | 1 | | | ALL |
| 011 | 20 | | PA | 1-5 | 49-61-11 | D03744 | | 1 | | | | | GD0006 | D.. | 2 | | ALL |
| 012 | 22 | | PA | 4-3 | 49-61-11 | D03744 | | 6 | | | | | TB0212Y | A005 | BJ | | ALL |
| 013 | 22 | | PA | 4-3 | 49-61-11 | D03744 | | 3 | | | | | TB0212Z | 20 | BJ | | ALL |
| 014 | 22 | | PA | 6-4 | 49-61-11 | D03744 | | 7 | | | | | D04056J | 13 | | | ALL |
| 015 | 22 | | PA | 6-8 | 49-61-11 | D03750 | | B1 | | | | | D04056J | 14 | | | ALL |
| 016 | 22 | | PA | 1-10 | 49-61-11 | D03750 | | B2 | | | | | TB0086Y | C004 | BJ | | ALL |
| 017 | 20 | | PA | 1-10 | 49-61-11 | D03750 | | X2 | | | | | TB0086Y | C004 | BJ | | ALL |
| 018 | 22 | | PA | 6-0 | 49-61-11 | TB0212X | | A002 | BJ | | | | D04056J | 4 | | | ALL |
| 019 | 22 | | PA | 6-0 | 49-61-11 | D04056J | | 10 | | | | | TB0212Y | A005 | BJ | | ALL |
| 021 | 22 | | PA | 6-0 | 49-61-11 | D04056J | | 12 | | | | | TB0212Z | 20 | BJ | | ALL |
| 022 | 22 | | PA | 5-3 | 49-61-11 | D04948J | | 11 | | | | | TB0212Z | 20 | BJ | | ALL |
| 023 | 20 | | PA | 1-6 | 28-25-21 | D03772 | | 3 | | | | | GD0006 | D.. | 2 | | ALL |
| 024 | 20 | | PA | 1-6 | 28-25-21 | D03772 | | 2 | | | | | GD0006 | D.. | 2 | | ALL |
| 025 | 22 | | PA | 6-1 | 28-25-21 | D03772 | | 7 | | | | | D05270J | 12 | | | ALL |
| 026 | 24 | | PK | 7-1 | SPARE | D05822J | | 9 | | | | | TB0086Y | C007 | BJ | | 150 |
| 027 | 24 | | PK | 7-1 | SPARE | D05822J | | 15 | | | | | TB0086Y | C007 | BJ | | 150 |
| 028 | 24 | | PV | AA | 4-4 | 73-21-11 | | 16 | | | | | TB0304X | B007 | BJ | | 050-099 |
| 028 | 24 | | PV | BI | 4-4 | 73-21-11 | | 16 | | | | | TB0304X | B007 | BJ | | 150-199, 277-299 |
| 028 | 24 | | PV | BI | 4-4 | 73-21-11 | | 16 | | | | | TB0304X | C008 | BJ | | 275-276 |
| 028Z | | | | AA | 0-0 | 73-21-11 | | 14 | | | | | TB0304X | B008 | BJ | | 050-099 |
| 028Z | | | | BI | 0-0 | 73-21-11 | | 14 | | | | | TB0304X | B008 | BJ | | 150-199, 277-299 |
| 028Z | | | | BI | 0-0 | 73-21-11 | | 14 | | | | | TB0304X | A009 | BJ | | 275-276 |
| 029 | 24 | | PK | | 4-9 | 31-31-22 | | 32 | | | | | TB0192X | C004 | BJ | | 050-099, 150-199 |
| 029 | 24 | | PK | | 4-9 | 31-31-22 | | 46 | | | | | TB0192X | C004 | BJ | | 275-299 |
| 02A | 24 | | PV | QD | 10-0 | 28-22-12 | | 12 | | | | | TB0212Y | A007 | BJ | | 150-199 |
| 02AZ | | | | QD | 0-0 | 28-22-12 | | D05052J | | DED | | | TB0212Y | DED | | | 150-199 |
| 030 | 22 | | PA | 6-9 | 28-25-21 | D03708 | | B3 | | | | | D05270J | 4 | | | 050-099 |
| 030 | 20 | | PA | 6-9 | 28-25-21 | D03708 | | B3 | | | | | D05270J | 4 | | | 150-199, 275-299 |
| 031 | 22 | | PA | 6-9 | 28-25-21 | D03708 | | B1 | | | | | D05270J | 3 | | | 050-099 |
| 031 | 20 | | PA | 6-9 | 28-25-21 | D03708 | | B1 | | | | | D05270J | 3 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 55

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0198 | 286T0198 | | | P37-S2-RIGHT MISC ELEC EQUIP PNL INTEG (continued) | | | | | | | | | | | |
| 032 | 24 | PV | H | 4-8 | 29-21-31 | D05270J | 19 | | | TB0190Y | A005 | BJ | | ALL | |
| 032Z | | | H | 0-0 | 29-21-31 | D05270J | DED | | | TB0190Y | DED | | | ALL | |
| 035 | 24 | PV | A | 4-3 | 29-21-31 | D05052J | 15 | | | TB0190X | C003 | BJ | | ALL | |
| 035Z | | | A | 0-0 | 29-21-31 | D05052J | DED | | | TB0190X | DED | | | ALL | |
| 037 | 24 | PK | | 1-9 | 29-21-31 | D05270J | 20 | | | D04958J | 2 | | | ALL | |
| 039 | 24 | PV | E | 1-9 | 29-21-31 | D05270J | 7 | | | D04958J | 5 | | | ALL | |
| 039Z | | | E | 0-0 | 29-21-31 | D05270J | DED | | | D04958J | DED | | | ALL | |
| 040 | 24 | PV | F | 4-8 | 29-21-31 | D05270J | 1 | | | TB0190X | B003 | BJ | | ALL | |
| 040Z | | | F | 0-0 | 29-21-31 | D05270J | DED | | | TB0190X | DED | | | ALL | |
| 041 | 24 | PK | | 5-4 | 29-21-31 | D05270J | 9 | | | TB0274D | C038 | 2 | | ALL | |
| 042 | 24 | PK | | 4-2 | 29-21-31 | D05270J | 8 | | | TB0304G | 33 | 2 | | ALL | |
| 043 | 24 | PK | | 4-2 | 31-31-22 | D04948J | 48 | | | TB0304X | B009 | BJ | | 050-099 | |
| 043 | 24 | PK | | 4-2 | 31-31-22 | D04948J | 35 | | | TB0304X | C007 | BJ | | 150-199 | |
| 043 | 24 | PK | | 4-2 | 31-31-22 | D04948J | 48 | | | TB0304X | C007 | BJ | | 275-299 | |
| 049 | 24 | PK | | 4-11 | 24-22-41 | D04056J | 3 | | | TB0190Y | C010 | BJ | | ALL | |
| 055R | 22 | PH | | 6-6 | 26-15-12 | D04948J | 6 | | | D03750 | C3 | | | ALL | |
| 058R | 22 | PH | | 6-3 | 26-15-12 | D04948J | 5 | | | D10210 | A1 | | | ALL | |
| 063 | 20 | PA | | 4-1 | 49-61-11 | D03750 | C1 | | | TB0190Y | C006 | BJ | | ALL | |
| 064 | 22 | PA | | 4-1 | 26-15-12 | D03750 | C2 | | | TB0190X | C014 | BJ | | ALL | |
| 068 | 24 | PK | | 3-5 | 29-11-32 | D04056J | 15 | | | D05052J | 9 | | | ALL | |
| 069 | 20 | PA | | 7-0 | 49-61-11 | D04948J | 8 | | | TB0086Y | C004 | BJ | | ALL | |
| 070 | 22 | PA | | 3-4 | 29-11-32 | D05052J | 7 | | | D04958J | 9 | | | ALL | |
| 074 | 20 | PA | | 1-8 | 28-25-11 | D03726 | | | FA | GDX0006 | S.. | 2 | | 050-099, 155-199, 276-299 | |
| 074 | 16 | PA | | 2-2 | 28-25-11 | D03726 | | | FA | GDX0011 | S.. | F | | 150-154, 275 | |
| 075 | 24 | PK | | 2-0 | 28-25-11 | D00428 | 8 | | | TB0086Y | C003 | BJ | | ALL | |
| 076 | 24 | PK | | 2-0 | 28-25-11 | D00428 | 5 | | | TB0086Y | A004 | BJ | | ALL | |
| 077 | 24 | PK | | 6-1 | 28-25-11 | D00428 | 1 | | | D05270J | 18 | | | ALL | |
| 078 | 24 | PK | | 2-0 | 28-25-11 | D00428 | 6 | | | TB0086Y | C003 | BJ | | ALL | |
| 079 | 24 | PK | | 2-0 | 28-25-11 | D00428 | 12 | | | TB0086Y | A002 | BJ | | ALL | |
| 080 | 24 | PK | | 2-0 | 28-25-11 | D00428 | 2 | | | TB0086Y | A002 | BJ | | ALL | |
| 081 | 24 | PK | | 1-11 | 28-25-11 | D00430 | A2 | | | TB0086Y | C002 | BJ | | ALL | |
| 082 | 24 | PK | | 6-6 | 28-25-11 | D05052J | 18 | | | TB0086Y | C002 | BJ | | ALL | |
| 083 | 24 | PK | | 1-11 | 28-25-11 | D00430 | X2 | | | TB0086Y | C002 | BJ | | ALL | |
| 084 | 16 | PQ | AB | 5-2 | 28-25-11 | D05052J | 1 | | | D03726 | A1 | | | ALL | |
| 084Z | | | AB | 0-0 | 28-25-11 | D03726 | | | FA | D05052J | 5 | | | ALL | |
| 085 | 24 | PK | | 1-11 | 28-25-11 | D00430 | X1 | | | TB0086Y | C003 | BJ | | ALL | |
| 086 | 24 | PK | | 1-11 | 28-25-11 | D00430 | A3 | | | TB0086Y | A002 | BJ | | ALL | |
| 088 | 24 | PK | | 5-2 | 28-25-11 | TB0274D | C019 | 2 | | D03726 | X1 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 56

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0198 | 286T0198 | | | P37-S2-RIGHT MISC ELEC EQUIP PNL INTEG (continued) | | | | | | | | | | | | | |
| 090 | 24 | | PK | 6-6 | 28-25-11 | D03726 | | X2 | | | | | D05052J | 21 | | | ALL |
| 091 | 16 | | PA | 5-2 | 28-25-11 | D03726 | | A2 | | | | | D05052J | 2 | | | ALL |
| 092 | 24 | | PK | 2-1 | 28-25-11 | D03708 | | C1 | | | | | TB0086Y | A004 | BJ | | ALL |
| 093 | 24 | | PK | 4-3 | 28-25-11 | D00428 | | 3 | | | | | TB0274D | A019 | 2 | | ALL |
| 106 | 22 | | PA | 4-2 | 28-25-21 | D03772 | | 4 | | | | | TB0212Y | A008 | BJ | | ALL |
| 107 | 18 | | PA | 3-2 | 27-11-12 | D05052J | | 24 | DK | | | | D05270J | 10 | DL | | ALL |
| 108 | 18 | | PA | 3-2 | 27-11-12 | D05052J | | 25 | DK | | | | D05270J | 6 | DL | | ALL |
| 109 | 20 | | PA | 3-2 | 27-11-12 | D05052J | | 26 | | | | | D05270J | 11 | | | ALL |
| 110 | 20 | | PA | 3-2 | 27-11-12 | D05052J | | 28 | | | | | D05270J | 5 | | | ALL |
| 111 | 24 | | PK | 5-1 | 28-22-11 | D05052J | | 17 | | | | | D00428 | 7 | | | ALL |
| 112 | 24 | | PK | 6-2 | 28-22-11 | D05188J | | 11 | | | | | D00428 | 14 | | | ALL |
| 113 | 22 | | PA | 6-11 | 28-25-11 | D05270J | | 16 | | | | | D03708 | C2 | | | 050-099 |
| 113 | 20 | | PA | 6-11 | 28-25-11 | D05270J | | 16 | | | | | D03708 | C2 | | | 150-199, 275-299 |
| 114 | 24 | | PK | 4-4 | 29-21-31 | D04958J | | 7 | | | | | TB0304G | 33 | 2 | | 050-099, 275-299 |
| 114 | 24 | | PK | 4-4 | 29-21-31 | D04958J | | 7 | DK | | | | TB0304G | 33 | 2 | | 150-199 |
| 115 | 24 | | PK | 3-4 | 29-21-31 | D04958J | | 3 | | | | | D05052J | 27 | | | ALL |
| 116 | 20 | | PA | 1-7 | 27-11-22 | D05037J | | 8 | | | | | D05188J | 7 | | | ALL |
| 117 | 20 | | PA | 1-7 | 27-11-22 | D05037J | | 9 | | | | | D05188J | 8 | | | ALL |
| 118 | 18 | | PA | 1-7 | 27-11-22 | D05037J | | 7 | | | | | D05188J | 9 | DL | | ALL |
| 119 | 18 | | PA | 1-7 | 27-11-22 | D05037J | | 10 | | | | | D05188J | 10 | DL | | ALL |
| 11A | 22 | | PA | 5-0 | 32-45-11 | D04745J | | 2 | | | | | TB0274X | C013 | BJ | | 050-099, 150-199 |
| 11B | 22 | | PA | 5-0 | 32-45-11 | D04745J | | 3 | | | | | TB0274X | B013 | BJ | | 050-099, 150-199 |
| 120 | 24 | | PK | 7-1 | 80-11-21 | D05822J | | 1 | | | | | TB0086Y | A001 | BJ | | ALL |
| 122 | 24 | | PK | 1-10 | 80-11-21 | D03702 | | X1 | | | | | TB0086Y | A001 | BJ | | ALL |
| 123 | 20 | | PA | 1-3 | 80-11-21 | D03702 | | X2 | | | | | GDX0006 | D.. | 2 | | ALL |
| 124 | 20 | | PA | 4-10 | 76-11-11 | D05822J | | 5 | | | | | TB0192Y | C013 | BJ | | ALL |
| 125 | 24 | | PK | 4-9 | 76-11-11 | TB0212Z | | 16 | BJ | | | | D02414 | X1 | | | ALL |
| 126 | 20 | | PA | 4-2 | 76-11-11 | TB0192Y | | C013 | BJ | | | | D02414 | A2 | | | ALL |
| 128 | 20 | | PA | 6-9 | 76-11-11 | D02414 | | A3 | | | | | D05822J | 11 | | | ALL |
| 129 | 20 | | PA | 1-11 | 76-11-11 | D02414 | | A1 | | | | | TB0086Y | C008 | BJ | | ALL |
| 130 | 20 | | PA | 1-4 | 76-11-11 | D02414 | | X2 | | | | | GDX0006 | D.. | 2 | | ALL |
| 132 | 22 | | PA | 4-7 | 31-31-11 | D03702 | | B2 | | | | | TB0210Y | A016 | BJ | | ALL |
| 133 | 22 | | PA | 4-7 | 31-31-11 | D03702 | | B1 | | | | | TB0210Y | C016 | BJ | | ALL |
| 134 | 20 | | PA | 5-5 | 76-11-11 | D05822J | | 29 | | | | | TB0212Z | 16 | BJ | | ALL |
| 136 | 20 | | PA | 5-5 | 76-11-11 | D05822J | | 22 | | | | | TB0274D | C035 | 2 | | ALL |
| 137 | 20 | | PA | 0-11 | 76-11-11 | TB0274D | | A035 | 2 | | | | TB0212Z | 16 | BJ | | ALL |
| 138 | 18 | | PA | 1-5 | 28-22-21 | D05822J | | 17 | DK | | | | D05188J | 15 | DL | | ALL |
| 139 | 18 | | PA | 1-5 | 28-22-21 | D05822J | | 18 | DK | | | | D05188J | 12 | DL | | ALL |
| 146 | 20 | | PA | 1-3 | 23-31-13 | D03702 | | C3 | | | | | GDX0006 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 57

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0198 | 286T0198 | | | P37-S2-RIGHT MISC ELEC EQUIP PNL INTEG (continued) | | | | | | | | | | | |
| 147 | 24 | | PK | 4-1 | 23-31-13 | D03702 | | C2 | | | TB0192X | B019 | BJ | | ALL |
| 148 | 20 | | PA | 5-5 | 76-11-11 | D05822J | | 6 | | | TB0212Z | 16 | BJ | | 050-099, 150-154, 275-276 |
| 148 | 24 | | PK | 5-5 | 76-11-11 | D05822J | | 6 | | | TB0212Z | 16 | BJ | | 155-199, 277-299 |
| 14H | 24 | | PK | 0-7 | SPARE | TB0086Y | | C007 | BJ | | TB0086D | C005 | 2 | | 150 |
| 150 | 22 | | PA | 1-5 | 28-22-21 | D05822J | | 20 | | | D05188J | 14 | | | ALL |
| 155 | 22 | | PA | 0-11 | 49-61-11 | TB0212Z | | 18 | BJ | | TB0274D | A022 | 2 | | ALL |
| 156R | 20 | | PH | 7-0 | 26-22-21 | D04948J | | 1 | | | TB0086Y | A003 | BJ | | ALL |
| 157R | 20 | | PH | 1-10 | 26-22-21 | TB0086Y | | A003 | BJ | | D03750 | A1 | | | ALL |
| 158R | 20 | | PH | 6-6 | 26-22-21 | D04948J | | 2 | | | D03750 | A2 | | | ALL |
| 159R | 20 | | PH | 1-10 | 49-61-11 | TB0086Y | | A003 | BJ | | D03750 | X1 | | | ALL |
| 169 | 24 | | PK | 6-9 | 80-11-21 | D02414 | | D2 | | | D05822J | 2 | | | ALL |
| 170 | 24 | | PK | 1-11 | 80-11-21 | D02414 | | D3 | | | TB0086Y | A001 | BJ | | ALL |
| 179 | 24 | | PK | 5-5 | 29-21-31 | D04958J | | 6 | | | TB0274D | C038 | 2 | | ALL |
| 180 | 16 | | PA | 4-10 | 27-09-13 | D05052J | | 4 | | | TB0274D | A038 | 2 | | ALL |
| 182 | 24 | | PK | 4-4 | 73-21-11 | D05822J | | 26 | | | TB0304X | A008 | BJ | | 050-099 |
| 182 | 24 | | PK | 4-4 | 73-21-11 | TB0304X | | A008 | BJ | | D05822J | 26 | | | 150-199, 275-299 |
| 183 | 24 | | PK | 4-4 | 73-21-11 | D05822J | | 27 | | | TB0304X | A007 | BJ | | 050-099 |
| 183 | 24 | | PK | 4-4 | 73-21-11 | TB0304X | | A007 | BJ | | D05822J | 27 | | | 150-199, 275-299 |
| 185 | 24 | | PK | 7-1 | 31-31-26 | D05822J | | 31 | | | TB0086Y | C008 | BJ | | ALL |
| 187 | 20 | | PA | 7-1 | 76-11-11 | D05822J | | 12 | | | TB0086Y | C008 | BJ | | 050-099 |
| 187 | 20 | | UA | 7-1 | 76-11-11 | D05822J | | 12 | | | TB0086Y | C008 | BJ | | 150-199, 275-299 |
| 189 | 24 | | PK | 9-3 | 28-22-12 | D05052J | | 23 | | | TB0082Y | A003 | BJ | | 050-099, 155-199, 276-299 |
| 189 | 24 | | PK | 10-0 | 28-22-12 | D05052J | | 23 | | | TB0212Y | C006 | BJ | | 150-154, 275 |
| 190 | 22 | | PA | 4-2 | 74-31-21 | TB0192X | | A010 | BJ | | D02414 | C2 | | | ALL |
| 191 | 22 | | PQ | L | 4-2 | 74-31-21 | TB0192X | B010 | BJ | | D02414 | B2 | | | ALL |
| 191Z | | | | L | 0-0 | 74-31-21 | TB0192X | DED | | | D02414 | DED | | | ALL |
| 192 | 22 | | PA | | 4-2 | 74-31-21 | TB0192X | C010 | BJ | | D02414 | C3 | | | ALL |
| 193 | 22 | | PQ | M | 4-2 | 74-31-21 | TB0192X | D010 | BJ | | D02414 | B3 | | | ALL |
| 193Z | | | | M | 0-0 | 74-31-21 | TB0192X | DED | | | D02414 | DED | | | ALL |
| 195R | 20 | | PH | 3-5 | 26-22-21 | D04948J | | 10 | | | D05378J | 1 | | | 275-299 |
| 197 | 24 | | PK | 5-4 | 36-11-41 | D04948J | | 17 | | | TB0274F | A032 | 2 | | ALL |
| 199 | 22 | | PA | 4-7 | 31-31-11 | D03702 | | B3 | | | TB0210X | D019 | BJ | | ALL |
| 200B | 20 | | PR | AD | 3-5 | 32-45-12 | D04745J | 14 | | | D04948J | 43 | | | 050-099 |
| 200B | 20 | | PR | AA | 3-5 | 32-45-12 | D04948J | 43 | | | D04745J | 14 | | | 150-199 |
| 200B | 20 | | PR | AC | 4-3 | 32-45-12 | D04948J | 43 | | | TB0320X | C036 | BJ | | 275-299 |
| 200R | 20 | | PR | AD | 0-0 | 32-45-12 | D04745J | 13 | | | D04948J | 42 | | | 050-099 |
| 200R | 20 | | PR | AA | 0-0 | 32-45-12 | D04948J | 42 | | | D04745J | 13 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 58

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|----------|-------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0198 | 286T0198 | | | P37-S2-RIGHT MISC ELEC EQUIP PNL INTEG (continued) | | | | | | | | | | | | |
| 200R | 20 | PR | AC | 0-0 | 32-45-12 | | D04948J | 42 | | | | TB0320X | B036 | BJ | | 275-299 |
| 200Z | | | AD | 0-0 | 32-45-12 | | D04745J | 15 | | | | D04948J | 44 | | | 050-099 |
| 200Z | | | AA | 0-0 | 32-45-12 | | D04948J | 44 | | | | D04745J | 15 | | | 150-199 |
| 200Z | | | AC | 0-0 | 32-45-12 | | D04948J | 44 | | | | TB0320X | D036 | BJ | | 275-299 |
| 201B | 22 | PB | G | 4-5 | 21-61-51 | | D04056J | 6 | | | | TB0304X | A004 | BJ | | ALL |
| 201R | 22 | PB | G | 0-0 | 21-61-51 | | D04056J | 7 | | | | TB0304X | B004 | BJ | | ALL |
| 202B | 24 | PL | J | 5-4 | 28-41-11 | | D05188J | 3 | | | | TB0212X | B003 | BJ | | ALL |
| 202R | 24 | PL | J | 0-0 | 28-41-11 | | D05188J | 2 | | | | TB0212X | A003 | BJ | | ALL |
| 205B | 24 | PW | K | 4-5 | 32-42-11 | | D04745J | 5 | | | | TB0190Y | C016 | BJ | | ALL |
| 205R | 24 | PW | K | 0-0 | 32-42-11 | | D04745J | 4 | | | | TB0190Y | A016 | BJ | | ALL |
| 205Z | | | K | 0-0 | 32-42-11 | | D04745J | 6 | | | | TB0190Y | C015 | BJ | | ALL |
| 207B | 20 | PR | AC | 4-11 | 32-45-12 | | D04745J | 11 | | | | TB0210X | B017 | BJ | | 050-099 |
| 207B | 20 | PR | AC | 4-11 | 32-45-12 | | TB0210X | | B017 | BJ | | D04745J | 11 | | | 150-199 |
| 207R | 20 | PR | AC | 0-0 | 32-45-12 | | D04745J | 10 | | | | TB0210X | A017 | BJ | | 050-099 |
| 207R | 20 | PR | AC | 0-0 | 32-45-12 | | TB0210X | | A017 | BJ | | D04745J | 10 | | | 150-199 |
| 207Z | | | AC | 0-0 | 32-45-12 | | D04745J | 12 | | | | TB0210X | C017 | BJ | | 050-099 |
| 207Z | | | AC | 0-0 | 32-45-12 | | TB0210X | | C017 | BJ | | D04745J | 12 | | | 150-199 |
| 500 | 20 | PA | | 5-3 | 25-33-11 | | D05270J | 41 | | | | TB0212Y | C005 | BJ | | 050-099, 155-199, 277-299 |
| 501 | 24 | PK | | 3-5 | 49-61-11 | | D05378J | 9 | | | | D04948J | 16 | | | ALL |
| 502 | 24 | PK | | 4-11 | 49-61-11 | | D05378J | 8 | | | | TB0212Y | A005 | BJ | | ALL |
| 50B | 22 | PA | | 6-0 | 49-61-11 | | D04056J | 19 | | | | TB0212X | B002 | BJ | | 050-099, 162-199, 275-299 |
| 50C | 24 | PK | | 6-0 | 24-27-41 | | D04056J | 9 | | | | TB0274X | D013 | BJ | | 050-099 |
| 50C | 24 | PK | | 6-0 | 24-27-41 | | TB0274X | | D013 | BJ | | D04056J | 9 | | | 162-199, 275-299 |
| 50D | 24 | PK | | 4-2 | 31-31-22 | | D04948J | 45 | | | | TB0304X | C009 | BJ | | 050-099 |
| 50D | 24 | PK | | 4-2 | 31-31-22 | | D04948J | 45 | | | | TB0304X | D007 | BJ | | 150-199, 275-299 |
| 515 | 24 | PK | | 6-0 | 28-25-21 | | D04056J | 11 | | | | TB0212Y | A008 | BJ | | ALL |
| 516 | 22 | PQ | AM | 3-3 | 28-31-12 | | D05052J | 6 | | | | TB0304D | A037 | 2 | | 050-099, 155-199, 276-299 |
| 516Z | | | AM | 0-0 | 28-31-12 | | D05052J | | DED | | | TB0304D | DED | | | 050-099, 155-199, 276-299 |
| 517 | 24 | PK | | 3-5 | 49-15-11 | | D04948J | 3 | | | | D05378J | 12 | | | ALL |
| 519 | 24 | PK | | 4-2 | 36-11-41 | | D04948J | 18 | | | | TB0304X | C004 | BJ | | ALL |
| 520 | 24 | PK | | 7-11 | 28-22-12 | | TB0082Y | | A003 | BJ | | K00330 | X2 | C | | 050-099, 155-199, 276-299 |
| 524 | 24 | PK | | 4-5 | 76-11-11 | | D05376J | 7 | | | | TB0192Y | C013 | BJ | | ALL |
| 525 | 24 | PK | | 5-0 | 76-11-11 | | D05376J | 6 | | | | TB0274D | C021 | 2 | | ALL |
| 526 | 24 | PK | | 3-5 | 29-21-31 | | D05376J | 4 | | | | TB0304G | 33 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 59

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0198 | 286T0198 | | | P37-S2-RIGHT MISC ELEC EQUIP PNL INTEG (continued) | | | | | | | | | | | | | |
| 527 | 24 | | PK | 4-11 | 27-51-61 | D10108 | | 4 | | | | | D05822J | 7 | | | ALL |
| 528 | 20 | | PA | 2-8 | 27-51-61 | D10108 | | 1 | | | | | GDX0006 | A.. | 2 | | ALL |
| 529 | 22 | | PA | 4-11 | 27-51-61 | D10108 | | 5 | | | | | D05822J | 8 | | | ALL |
| 530 | 20 | | PA | 2-8 | 27-51-61 | D10108 | | 6 | | | | | GDX0006 | S.. | 2 | | ALL |
| 531 | 22 | | PA | 4-8 | 49-61-11 | D05270J | | 17 | | | | | TB0190Y | C006 | BJ | | ALL |
| 532 | 22 | | PA | 4-9 | 49-61-11 | D04948J | | 14 | | | | | TB0190Y | C006 | BJ | | ALL |
| 533R | 22 | | PH | 5-4 | 26-15-12 | D04948J | | 15 | | | | | TB0274D | A024 | 2 | | ALL |
| 534R | 22 | | PH | 6-3 | 26-15-12 | D04948J | | 21 | | | | | D10210 | X2 | | | ALL |
| 535R | 22 | | PH | 4-5 | 26-15-12 | D10210 | | X1 | | | | | TB0274D | C024 | 2 | | ALL |
| 536R | 22 | | PH | 4-5 | 26-15-12 | D10210 | | A2 | | | | | TB0274D | A024 | 2 | | ALL |
| 537R | 20 | | PH | 3-5 | 26-21-11 | D04948J | | 13 | | | | | D05378J | 2 | | | ALL |
| 538R | 20 | | PH | 3-4 | 26-23-12 | D04948J | | 4 | | | | | D05376J | 3 | | | 050-099, 155-199, 275-299 |
| 538R | 20 | | PH | 3-4 | 26-23-11 | D04948J | | 4 | | | | | D05376J | 3 | | | 150-154 |
| 539R | 20 | | PH | 3-4 | 26-21-11 | D05270J | | 14 | | | | | D05376J | 2 | | | ALL |
| 540R | 20 | | PH | 3-4 | 26-23-11 | D05270J | | 15 | | | | | D05378J | 11 | | | ALL |
| 542R | 20 | | PH | 3-5 | 26-22-21 | D04948J | | 19 | | | | | D05378J | 10 | | | ALL |
| 548 | 24 | | PK | 3-5 | 36-11-41 | D05378J | | 7 | | | | | TB0304Y | C012 | BJ | | ALL |
| 549 | 22 | | PQ | AN | 4-9 | 28-42-13 | D05052J | 10 | | | | | TB0210X | D009 | BJ | | 050-099, 155-199, 276-299 |
| 549Z | | | | AN | 0-0 | 28-42-13 | D05052J | DED | | | | | TB0210X | DED | | | 050-099, 155-199, 276-299 |
| 553 | 24 | | PK | 4-11 | 28-25-21 | D05378J | | 4 | | | | | TB0212Y | A008 | BJ | | ALL |
| 554 | 24 | | PK | 6-6 | 28-25-11 | D05052J | | 32 | | | | | TB0086Y | C003 | BJ | | ALL |
| 555 | 24 | | PK | 6-6 | 28-25-11 | D05052J | | 31 | | | | | TB0086Y | A004 | BJ | | ALL |
| 556 | 22 | | PA | 3-4 | 26-16-21 | D04948J | | 20 | | | | | D05376J | 8 | | | ALL |
| 557 | 22 | | PA | 3-4 | 26-16-21 | D04948J | | 22 | | | | | D05376J | 9 | | | ALL |
| 558 | 22 | | PA | 5-4 | 26-16-21 | D04948J | | 23 | | | | | TB0274D | C016 | 2 | | ALL |
| 559 | 22 | | PA | 5-4 | 26-16-21 | D04948J | | 24 | | | | | TB0274D | C017 | 2 | | ALL |
| 560 | 22 | | PA | 5-0 | 26-16-21 | D05378J | | 3 | | | | | TB0274D | A016 | 2 | | ALL |
| 561 | 22 | | PA | 0-7 | 26-16-21 | TB0274D | | A016 | 2 | | | | TB0274D | A017 | 2 | | ALL |
| 562R | 22 | | PH | 6-2 | 26-17-11 | D01178 | | 1 | | | | | D04948J | 29 | | | ALL |
| 563R | 22 | | PH | 6-2 | 26-17-11 | D01178 | | 6 | | | | | D04948J | 27 | | | ALL |
| 564R | 22 | | PH | 6-2 | 26-17-11 | D01178 | | 12 | | | | | D04948J | 28 | | | 050-099, 151, 275-299 |
| 564R | 22 | | PH | 6-0 | 26-17-11 | D01178 | | 12 | | | | | TB0304D | A38 | 2 | | 150, 152-199 |
| 565R | 20 | | PH | 1-5 | 26-17-11 | D01178 | | 4 | | | | | GDX0006 | D.. | 2 | | 050-099, 150-199, 277-278 |
| 565R | 20 | | PH | 1-5 | 26-17-11 | D01178 | | 4 | | | | | GDX0006 | D.. | 2 | * | 275 |
| 565R | 20 | | PH | 1-5 | 26-17-11 | D01178 | | 4 | | | | | GDX0006 | D.. | 2 | *2 | 276, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 60

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0198 | 286T0198 | | | P37-S2-RIGHT MISC ELEC EQUIP PNL INTEG (continued) | | | | | | | | | | | | | |
| 566R | 20 | | PH | 1-5 | 26-17-11 | D01178 | | 2 | | | | | GDX0006 | D.. | 2 | | 050-099, 150-199, 277-278 |
| 566R | 20 | | PH | 1-5 | 26-17-11 | D01178 | | 2 | | | | | GDX0006 | D.. | 2 | * | 275 |
| 566R | 20 | | PH | 1-5 | 26-17-11 | D01178 | | 2 | | | | | GDX0006 | D.. | 2 | *2 | 276, 280-299 |
| 567R | 22 | | PH | 4-2 | 26-17-11 | TB0304X | | | D006 | | BJ | | D05270J | | 27 | | ALL |
| 568R | 22 | | PH | 3-2 | 26-17-11 | D05052J | | 11 | | | | | D05270J | | 28 | | ALL |
| 569R | 22 | | PH | 6-2 | 26-17-11 | D01178 | | 5 | | | | | D04948J | | 30 | | ALL |
| 570 | 22 | | PA | 5-3 | 25-33-11 | D05270J | | 31 | | | | | TB0210X | A019 | BJ | | 050-099 |
| 570 | 22 | | PA | 5-3 | 21-58-16 | TB0210X | | | A019 | | BJ | | D05270J | | 31 | | 150-152, 275-276 |
| 570 | 22 | | PA | 5-3 | 25-33-11 | TB0210X | | | A019 | | BJ | | D05270J | | 31 | | 153-199, 277-299 |
| 571 | 24 | | PK | 5-3 | 21-58-16 | D04948J | | 31 | | | | | TB0210X | B019 | BJ | | ALL |
| 574R | 20 | | PH | 2-5 | 26-23-12 | D10664 | | | A2 | | | | TB0262Z | 7 | BJ | | 150-199, 275-299 |
| 575R | 20 | | PH | 2-5 | 26-23-12 | D10664 | | | C2 | | | | TB0262Z | 7 | BJ | | 150-199, 275-299 |
| 576R | 20 | | PH | 2-5 | 26-23-12 | D10664 | | | D2 | | | | TB0262D | C001 | 2 | | 150-154 |
| 576R | 20 | | PH | 2-5 | 26-23-12 | D10664 | | | D2 | | | | TB0262G | 1 | 2 | | 155-199, 275-299 |
| 577R | 20 | | PH | 2-5 | 26-23-12 | D10664 | | | X1 | | | | TB0262D | C001 | 2 | | 150-154 |
| 577R | 20 | | PH | 2-5 | 26-23-12 | D10664 | | | X1 | | | | TB0262G | 1 | 2 | | 155-199, 275-299 |
| 578R | 20 | | PH | 8-4 | 26-23-12 | D10664 | | | X2 | | | | D05270J | 13 | | | 150-199, 275-299 |
| 579R | 20 | | PH | 9-8 | 26-23-12 | D04948J | | 25 | | | | | TB0262Y | C003 | BJ | | 050-099 |
| 579R | 20 | | PH | 9-8 | 26-23-12 | D04948J | | 25 | | | | | TB0262D | A001 | 2 | | 150-154 |
| 579R | 20 | | PH | 9-8 | 26-23-12 | D04948J | | 25 | | | | | TB0262G | 1 | 2 | | 155-199, 275-299 |
| 580R | 20 | | PH | 9-8 | 26-23-12 | D04948J | | 34 | | | | | TB0262Y | A003 | BJ | | 050-099 |
| 580R | 20 | | PH | 9-8 | 26-23-12 | D04948J | | 34 | | | | | TB0262D | A002 | 2 | | 150-154 |
| 580R | 20 | | PH | 9-8 | 26-23-12 | D04948J | | 34 | | | | | TB0262G | 2 | 2 | | 155-199, 275-299 |
| 581R | 20 | | PH | 2-4 | 26-23-12 | D10666 | | | B2 | | | | TB0262Z | 7 | BJ | | 150-199, 275-299 |
| 582R | 20 | | PH | 2-4 | 26-23-12 | D10666 | | | C2 | | | | TB0262Z | 7 | BJ | | 150-199, 275-299 |
| 583R | 20 | | PH | 2-4 | 26-23-12 | D10666 | | | D2 | | | | TB0262D | C002 | 2 | | 150-154 |
| 583R | 20 | | PH | 2-4 | 26-23-12 | D10666 | | | D2 | | | | TB0262G | 2 | 2 | | 155-199, 275-299 |
| 584R | 20 | | PH | 2-4 | 26-23-12 | D10666 | | | X1 | | | | TB0262D | C002 | 2 | | 150-154 |
| 584R | 20 | | PH | 2-4 | 26-23-12 | D10666 | | | X1 | | | | TB0262G | 2 | 2 | | 155-199, 275-299 |
| 585R | 20 | | PH | 8-5 | 26-23-12 | D10666 | | | X2 | | | | D04948J | 33 | | | 150-199, 275-299 |
| 586R | 20 | | PH | 2-5 | 26-23-12 | D10664 | | | A1 | | | | TB0262Y | A003 | BJ | | 150-199, 275-299 |
| 587R | 20 | | PH | 1-1 | 26-23-12 | D10664 | | | C3 | | | | D10666 | D1 | | | 150-199, 275-299 |
| 588R | 20 | | PH | 2-5 | 26-23-12 | D10664 | | | C1 | | | | TB0262Y | A004 | BJ | | 150-199, 275-299 |
| 589R | 20 | | PH | 1-1 | 26-23-12 | D10664 | | | D1 | | | | D10666 | C3 | | | 150-199, 275-299 |
| 590R | 20 | | PH | 2-4 | 26-23-12 | D10666 | | | B1 | | | | TB0262Y | C003 | BJ | | 150-199, 275-299 |
| 591R | 20 | | PH | 2-4 | 26-23-12 | D10666 | | | C1 | | | | TB0262Y | A004 | BJ | | 150-199, 275-299 |
| 592R | 20 | | PH | 9-8 | 26-23-12 | D04948J | | 26 | | | | | TB0262Y | C003 | BJ | | 050-099 |
| 592R | 20 | | PH | 8-4 | 26-23-12 | D04948J | | 26 | | | | | D10664 | B2 | | | 155-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 61

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|---------|-------|------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0198 | 286T0198 | | | P37-S2-RIGHT MISC ELEC EQUIP PNL INTEG (continued) | | | | | | | | | | | |
| 593R | 20 | | PH | | 9-8 | 26-23-12 | D04948J | | 35 | | TB0262Y | A003 | BJ | | 050-099 |
| 593R | 20 | | PH | | 8-5 | 26-23-12 | D04948J | | 50 | | D10666 | A2 | | | 155-199 |
| 593R | 20 | | PH | | 8-5 | 26-23-12 | D10666 | | A2 | | D04948J | 35 | | | 275-299 |
| 594R | 20 | | PH | | 1-7 | 26-23-12 | D10668 | | A2 | | TB0262Y | A003 | BJ | | 150-199, 275-299 |
| 595R | 20 | | PH | | 1-7 | 26-23-12 | D10668 | | B2 | | TB0262Y | C003 | BJ | | 150-199, 275-299 |
| 596R | 20 | | PH | | 1-7 | 26-23-12 | D10668 | | X1 | | TB0262Y | A004 | BJ | | 150-199, 275-299 |
| 597R | 20 | | PH | | 1-3 | 26-23-12 | D10668 | | X2 | | GDX0014 | D.. | 2 | | 150-199, 275-299 |
| 598R | 20 | | PH | | 9-8 | 26-23-12 | D04948J | | 38 | | TB0262Z | 7 | BJ | | 150-199, 275-299 |
| 599 | 20 | | PQ | AE | 4-11 | 25-33-11 | D04056J | | 23 | | TB0192X | D008 | BJ | | 050-099 |
| 599 | 20 | | PQ | AP | 4-11 | 25-33-11 | D04056J | | 23 | | TB0192X | D008 | BJ | | 155-199, 277-299 |
| 599Z | | | | AE | 0-0 | 25-33-11 | D04056J | | DED | | TB0192X | DED | | | 050-099 |
| 599Z | | | | AP | 0-0 | 25-33-11 | D04056J | | DED | | TB0192X | DED | | | 155-199, 277-299 |
| 600R | 20 | | PH | | 1-7 | 26-23-12 | D10668 | | A1 | | TB0262Y | C004 | BJ | | 150-154 |
| 600R | 20 | | PH | | 1-7 | 26-23-12 | D10668 | | A1 | | TB0262Z | 5 | BJ | | 155-199, 275-299 |
| 601R | 20 | | PH | | 1-7 | 26-23-12 | D10668 | | B1 | | TB0262Y | A005 | BJ | | 150-154 |
| 601R | 20 | | PH | | 1-7 | 26-23-12 | D10668 | | B1 | | TB0262Z | 8 | BJ | | 155-199, 275-299 |
| 603 | 20 | | PQ | FA | 6-0 | 76-11-11 | D13826 | | X2 | | GDX0014 | D.. | 2 | | 050-099, 150-154, 275-276 |
| 603 | 20 | | PQ | FA | 8-9 | 76-11-11 | D13826 | | X2 | | GDX0014 | D.. | 2 | | 155-199, 280-299 |
| 603 | 20 | | PQ | FA | 5-3 | 76-11-11 | D13826 | | X2 | | GDX0014 | D.. | 2 | | 277-278 |
| 603Z | | | | FA | 0-0 | 76-11-11 | D13826 | | DED | | GDX0014 | DED | | | ALL |
| 604 | 24 | | PV | FB | 6-0 | 76-11-11 | D13826 | | X1 | | TB0212Z | 16 | BJ | | 050-099, 150-154, 275-276 |
| 604 | 24 | | PV | FB | 10-8 | 76-11-11 | D13826 | | X1 | | TB0212Z | 16 | BJ | | 155-199, 280-299 |
| 604 | 24 | | PV | FB | 6-8 | 76-11-11 | D13826 | | X1 | | TB0212Z | 16 | BJ | | 277-278 |
| 604Z | | | | FB | 0-0 | 76-11-11 | D13826 | | DED | | TB0212Z | DED | | | ALL |
| 605R | 20 | | PH | | 9-8 | 26-23-12 | D04948J | | 39 | | TB0262Y | C004 | BJ | | 150-154 |
| 605R | 20 | | PH | | 9-8 | 26-23-12 | D04948J | | 39 | | TB0262Z | 5 | BJ | | 155-199, 275-299 |
| 606R | 20 | | PH | | 9-8 | 26-23-12 | D04948J | | 36 | | TB0262Y | C004 | BJ | | 150-154 |
| 606R | 20 | | PH | | 9-8 | 26-23-12 | D04948J | | 36 | | TB0262Z | 5 | BJ | | 155-199, 275-299 |
| 607R | 20 | | PH | | 9-8 | 26-23-12 | D04948J | | 40 | | TB0262Y | A005 | BJ | | 150-154 |
| 607R | 20 | | PH | | 9-8 | 26-23-12 | D04948J | | 40 | | TB0262Z | 8 | BJ | | 155-199, 275-299 |
| 608R | 20 | | PH | | 9-8 | 26-23-12 | D04948J | | 37 | | TB0262Y | A005 | BJ | | 150-154 |
| 608R | 20 | | PH | | 9-8 | 26-23-12 | D04948J | | 37 | | TB0262Z | 8 | BJ | | 155-199, 275-299 |
| 609R | 20 | | PH | | 1-7 | 26-23-12 | D10862 | | B1 | | TB0262Y | A003 | BJ | | 050-099 |
| 610R | 20 | | PH | | 1-7 | 26-23-12 | D10862 | | A1 | | TB0262Y | C003 | BJ | | 050-099 |
| 611R | 20 | | PH | | 9-3 | 26-23-12 | D10862 | | X1 | | D05270J | 13 | | | 050-099 |
| 613R | 20 | | PH | | 1-3 | 26-23-12 | D10862 | | X2 | | GDX0014 | D.. | 2 | | 050-099 |
| 614R | 20 | | PH | | 9-3 | 26-23-12 | D10862 | | B3 | | D04948J | 40 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 62

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0198 | 286T0198 | | | P37-S2-RIGHT MISC ELEC EQUIP PNL INTEG (continued) | | | | | | | | | | | | | |
| 615R | 20 | | PH | 9-3 | 26-23-12 | D10862 | | B2 | | | | | D04948J | 37 | | | 050-099 |
| 616R | 20 | | PH | 9-3 | 26-23-12 | D10862 | | A3 | | | | | D04948J | 39 | | | 050-099 |
| 617R | 20 | | PH | 9-3 | 26-23-12 | D10862 | | A2 | | | | | D04948J | 36 | | | 050-099 |
| 618R | 20 | | PH | 8-5 | 26-23-12 | D04948J | | 49 | | | | | D10666 | A3 | | | 155-199 |
| 618R | 20 | | PH | 8-5 | 26-23-12 | D10666 | | A3 | | | | | D04948J | 32 | | | 275-299 |
| 619R | 20 | | PH | 2-5 | 26-23-12 | D10664 | | B1 | | | | | TB0262Z | 5 | BJ | | 155-199, 275-299 |
| 620R | 20 | | PH | 8-4 | 26-23-12 | D05270J | | 25 | | | | | D10664 | B3 | | | 155-199 |
| 620R | 20 | | PH | 8-4 | 26-23-12 | D10664 | | B3 | | | | | D05270J | 25 | | | 275-299 |
| 621R | 20 | | PH | 2-4 | 26-23-12 | D10666 | | A1 | | | | | TB0262Z | 8 | BJ | | 155-199 |
| 621R | 20 | | PH | 2-4 | 26-23-12 | TB0262Z | | 8 | BJ | | | | D10666 | A1 | | | 275-299 |
| 622 | 20 | | PQ | AF | 13-4 | 25-33-11 | D04056J | 18 | | | | | TB0254Y | C006 | BJ | | 050-099 |
| 622 | 20 | | PA | | 6-0 | 25-31-12 | D04056J | 16 | | | | | TB0254F | C017 | BJ | | 150-152 |
| 622 | 20 | | PA | | 4-11 | 25-31-12 | D04056J | 16 | | | | | TB0192X | A011 | BJ | | 153-154 |
| 622 | 20 | | PQ | AO | 4-6 | SPARE | D04056J | 17 | | | | | TB0320X | D006 | BJ | | 280-299 |
| 622Z | | | | AF | 0-0 | 25-33-11 | D04056J | DED | | | | | TB0254Y | DED | | | 050-099 |
| 622Z | | | | AO | 0-0 | SPARE | D04056J | DED | | | | | TB0320 | DED | | | 280-299 |
| 623 | 20 | | PA | | 6-0 | 25-31-12 | D04056J | 18 | | | | | TB0254F | A017 | BJ | | 150-152 |
| 623 | 20 | | PA | | 4-11 | 25-31-12 | D04056J | 18 | | | | | TB0192X | C019 | BJ | | 153-154 |
| 625 | 18 | | PQ | FC | 8-0 | 24-11-21 | D13826 | A2 | | | | | D05822J | 28 | DK | | 050-099 |
| 625 | 18 | | PQ | FC | 14-0 | 24-11-21 | D13826 | A2 | | | | | D05822J | 28 | DK | | 150-154, 275-276 |
| 625 | 18 | | PQ | FC | 12-2 | 24-11-21 | D13826 | A2 | | | | | D05822J | 28 | DK | | 155-199, 280-299 |
| 625 | 18 | | PQ | FC | 8-2 | 24-11-21 | D13826 | A2 | | | | | D05822J | 28 | DK | | 277-278 |
| 625Z | | | | FC | 0-0 | 24-11-21 | D13826 | DED | | | | | D05822J | DED | | | ALL |
| 626 | 18 | | PQ | FD | 8-0 | 24-11-21 | D13826 | A3 | | | | | D05822J | 10 | DK | | 050-099 |
| 626 | 18 | | PQ | FD | 14-0 | 24-11-21 | D13826 | A3 | | | | | D05822J | 10 | DK | | 150-154, 275-276 |
| 626 | 18 | | PQ | FD | 12-2 | 24-11-21 | D13826 | A3 | | | | | D05822J | 10 | DK | | 155-199, 280-299 |
| 626 | 18 | | PQ | FD | 8-2 | 24-11-21 | D13826 | A3 | | | | | D05822J | 10 | DK | | 277-278 |
| 626Z | | | | FD | 0-0 | 24-11-21 | D13826 | DED | | | | | D05822J | DED | | | ALL |
| 634 | 20 | | PQ | AU | 5-5 | 78-34-21 | D05822J | 4 | | | | | TB0274Y | A004 | BJ | | ALL |
| 634Z | | | | AU | 0-0 | 78-34-21 | D05822J | DED | | | | | TB0274Y | DED | | | ALL |
| 901 | 22 | | PH | | 6-0 | 26-17-11 | D04948J | 28 | | | | | TB0304D | C38 | 2 | | 150, 152-199 |
| 91M | 20 | | PA | | 5-5 | 76-11-11 | D05822J | 21 | | | | | TB0274Y | C004 | BJ | | 050-099, 275-299 |
| 91M | 20 | | PA | | 4-4 | 76-11-11 | D05822J | 21 | | | | | TB0304Y | C019 | BJ | | 150-199 |
| 91N | 20 | | PA | | 5-5 | 76-11-11 | D05822J | 19 | | | | | TB0274Y | C004 | BJ | | 050-099 |
| 91N | 20 | | PA | | 4-4 | 76-11-11 | TB0304Y | C019 | BJ | | | | D05822J | 19 | | | 150-199 |
| 91N | 20 | | PA | | 5-5 | 76-11-11 | TB0274Y | C004 | BJ | | | | D05822J | 15 | | | 275-299 |
| PA1 | | | | | 0-0 | 99-99-99 | D03726 | G2 | | | | | D03726 | G3 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0190

Page 63 End

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0201 | 286T0201 | | | POWER DISTRIBUTION LEFT, P11 TO E1 | | | | | | | | | | | | |
| 003 | 22 | | PA | | 36-0 | 27-41-11 | D04271P | | | | D05495P | | | | 3 | ALL |
| 005 | 22 | | PA | | 36-0 | 27-21-12 | D04271P | | | | D05495P | | | | 5 | ALL |
| 006 | 20 | | PA | | 38-0 | 34-45-11 | D04271P | | | | D04207J | | | | 23 | 050-099, 153-199, 277-299 |
| 006 | 20 | | PA | | 38-0 | 34-45-11 | D04271P | | 10 | | D04207J | | | | 23 | 150-152 |
| 007 | 20 | | PA | | 36-0 | SPARE | D04271P | | 7 | | D05495P | | | | 2 | ALL |
| 009 | 20 | | PA | | 36-0 | 22-41-12 | D04271P | | 9 | | D04281J | | | | 1 | ALL |
| 011 | 24 | | PK | | 36-0 | 34-22-16 | D04271P | | 11 | | D04281J | | | | 2 | ALL |
| 012 | 20 | | PA | | 36-0 | 34-22-16 | D04271P | | 12 | | D04281J | | | | 3 | ALL |
| 013 | 20 | | PA | | 38-0 | 22-11-11 | D04271P | | 13 | | D04207J | | | | 1 | ALL |
| 014 | 20 | | PA | | 38-0 | 22-11-12 | D04271P | | 14 | | D04207J | | | | 2 | ALL |
| 015 | 20 | | PA | | 38-0 | 22-11-12 | D04271P | | 15 | | D04207J | | | | 3 | ALL |
| 016 | 20 | | PA | | 38-0 | 22-31-11 | D04271P | | 16 | | D04207J | | | | 4 | ALL |
| 017 | 20 | | PA | | 38-0 | 22-31-12 | D04271P | | 17 | | D04207J | | | | 5 | ALL |
| 018 | 20 | | PA | | 38-0 | 22-31-12 | D04271P | | 18 | | D04207J | | | | 6 | ALL |
| 019 | 22 | | PA | | 38-0 | SPARE | D04271P | | 19 | | D04207J | | | | 7 | ALL |
| 020 | 22 | | PA | | 38-0 | SPARE | D04271P | | 20 | | D04207J | | | | 8 | ALL |
| 021 | 22 | | PA | | 38-0 | SPARE | D04271P | | 21 | | D04207J | | | | 9 | ALL |
| 022 | 22 | | PA | | 38-0 | SPARE | D04271P | | 22 | | D04207J | | | | 10 | ALL |
| 023 | 22 | | PA | | 38-0 | 34-31-11 | D04271P | | 23 | | D04207J | | | | 11 | ALL |
| 024 | 24 | | PK | | 38-0 | 27-48-11 | D04271P | | 24 | | D04207J | | | | 12 | ALL |
| 025 | 20 | | PA | | 38-0 | SPARE | D04271P | | 25 | | D04207J | | | | 13 | ALL |
| 026 | 20 | | PA | | 39-0 | SPARE | D04271P | | 26 | | D04205J | | | | 2 | ALL |
| 027 | 24 | | PK | | 39-0 | 34-22-36 | D04271P | | 27 | | D04205J | | | | 1 | ALL |
| 028 | 20 | | PA | | 40-0 | SPARE | D04271P | | 28 | | D04203J | | | | 2 | 050-099, 151 |
| 028 | 20 | | PA | | 40-0 | 34-46-13 | D04271P | | 28 | | D04203J | | | | 2 | 150, 152-199, 275-299 |
| 029 | 22 | | PA | | 40-0 | 34-46-11 | D04271P | | 29 | | D04203J | | | | 1 | ALL |
| 030 | 20 | | PA | | 41-0 | SPARE | D04271P | | 30 | | D04201J | | | | 2 | ALL |
| 031 | 24 | | PK | | 41-0 | 34-21-11 | D04271P | | 31 | | D04201J | | | | 1 | ALL |
| W0202 | 286T0202 | | | P31 TO NO.1 ELEC HYD PUMP L1-115 VAC POWER DISTRIBUTION | | | | | | | | | | | | |
| 004 | 08 | | HA | | 4-0 | 29-11-31 | SM00006 | | | | D00482 | | | | A | ALL |
| 005 | 08 | | HA | | 4-0 | 29-11-31 | SM00007 | | | | D00482 | | | | B | ALL |
| 006 | 08 | | HA | | 4-0 | 29-11-31 | SM00008 | | | | D00482 | | | | C | ALL |
| 011 | 06 | | QY | | 89-0 | 29-11-31 | M00897 | | A2 | H6 | SM00006 | | | GE | | 050-099 |
| 011 | 06 | | QY | | 96-0 | 29-11-31 | M00897 | | A2 | H6 | SM00006 | | | GE | | 150-199, 275-299 |
| 012 | 06 | | QY | | 89-0 | 29-11-31 | M00897 | | B2 | H6 | SM00007 | | | GE | | 050-099 |
| 012 | 06 | | QY | | 96-10 | 29-11-31 | M00897 | | B2 | H6 | SM00007 | | | GE | | 150-199, 275-299 |
| 013 | 06 | | QY | | 89-0 | 29-11-31 | M00897 | | C2 | H6 | SM00008 | | | GE | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0200
Page 1
Mar 14/2007



| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|---------|------|------|---------|-------|-------------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0202 | 286T0202 | | | P31 TO NO.1 ELEC HYD PUMP L1-115 VAC POWER DISTRIBUTION (continued) | | | | | | | | | | | |
| 013 | 06 | | QY | | 96-11 | 29-11-31 | M00897 | C2 | H6 | | SM00008 | | GE | | 150-199, 275-299 |
| 021 | 08 | | HA | | 3-0 | 29-11-31 | GD03500 | S.. | E* | | D00482 | D | | | ALL |
| 026 | 18 | | PA | | 84-0 | | SPARE | D05512J | | 6 | D05892P | 6 | | | 050-099 |
| 026 | 18 | | PA | | 95-0 | | SPARE | D05512J | | 6 | D05892P | 6 | | | 150-199, 275-299 |
| 034 | 14 | | PA | | 84-0 | 28-22-11 | D05892P | 1 | FN | | D05512J | 2 | FO | | 050-099 |
| 034 | 14 | | PA | | 95-0 | 28-22-11 | D05892P | 1 | FN | | D05512J | 2 | FO | | 150-199, 275-299 |
| 035 | 14 | | PA | | 84-0 | 28-22-11 | D05892P | 2 | FN | | D05512J | 3 | FO | | 050-099 |
| 035 | 14 | | PA | | 95-0 | 28-22-11 | D05892P | 2 | FN | | D05512J | 3 | FO | | 150-199, 275-299 |
| 036 | 14 | | PA | | 84-0 | 28-22-11 | D05892P | 3 | FN | | D05512J | 4 | FO | | 050-099 |
| 036 | 14 | | PA | | 95-0 | 28-22-11 | D05892P | 3 | FN | | D05512J | 4 | FO | | 150-199, 275-299 |
| 801 | 18 | | PA | | 84-0 | | SPARE | D05512J | | 7 | D05892P | 7 | | | 050-099 |
| 801 | 18 | | PA | | 95-0 | | SPARE | D05512J | | 7 | D05892P | 7 | | | 150-199, 275-299 |
| W0203 | 286T0203 | | | POWER DISTRIBUTION, P11 TO E2 & FLIGHT DECK | | | | | | | | | | | |
| 001 | 22 | | PA | | 33-0 | 34-51-11 | D04185P | 1 | | | D04233J | 1 | | | ALL |
| 002 | 20 | | PA | | 33-0 | | SPARE | D04185P | | 2 | D04233J | 2 | | | ALL |
| 003 | 22 | | PA | | 33-0 | 34-61-16 | D04185P | 3 | | | D04233J | 3 | | | ALL |
| 004 | 22 | | PA | | 10-0 | 23-51-21 | D04185P | 4 | | | SP00129 | | 9 | | ALL |
| 005 | 22 | | PA | | 18-0 | 34-57-21 | D04185P | 5 | | | SP00371 | | 9 | | ALL |
| 006 | 24 | | PK | | 7-0 | 31-51-11 | D04185P | 6 | | | SP00037 | | 9 | | ALL |
| 008 | 22 | | PA | | 35-0 | 23-42-11 | D04185P | 8 | | | D04227J | 1 | | | ALL |
| 009 | 22 | | PA | | 35-0 | 23-51-11 | D04185P | 9 | | | D04227J | 2 | | | ALL |
| 010 | 20 | | PA | | 35-0 | | SPARE | D04185P | | 10 | D04227J | 3 | | | ALL |
| 014 | 18 | | PA | | 32-0 | 27-11-22 | D04185P | 14 | | | SP00225 | | 9 | | ALL |
| 016 | 16 | | PA | | 35-0 | 23-12-11 | D04185P | 16 | | | D04227J | 4 | | | ALL |
| 018 | 18 | | PA | | 35-0 | 23-31-11 | D04185P | 18 | | | D04227J | 7 | | | ALL |
| W0204 | 286T0204 | | | FWD TO P31-L1-L GEN POWER FEEDER | | | | | | | | | | | |
| 001 | *1 | | HA | | 22-0 | 24-21-11 | G00019 | T1 | R | | SM00001 | | GJ | | 050-099 |
| 001 | *1 | | HA | | 21-0 | 24-21-11 | G00019 | T1 | R | | SM00001 | | GJ | | 150-154, 275 |
| 001 | *1 | | HA | | 21-1 | 24-21-11 | G00019 | T1 | R | | SM00001 | | GJ | | 155-199, 276-299 |
| 002 | *1 | | HA | | 22-0 | 24-21-11 | G00019 | T2 | R | | SM00002 | | GJ | | 050-099 |
| 002 | *1 | | HA | | 21-0 | 24-21-11 | G00019 | T2 | R | | SM00002 | | GJ | | 150-154, 275 |
| 002 | *1 | | HA | | 21-2 | 24-21-11 | G00019 | T2 | R | | SM00002 | | GJ | | 155-199, 276-299 |
| 003 | *1 | | HA | | 22-0 | 24-21-11 | G00019 | T3 | R | | SM00003 | | GJ | | 050-099 |
| 003 | *1 | | HA | | 21-0 | 24-21-11 | G00019 | T3 | R | | SM00003 | | GJ | | 150-154, 275 |
| 003 | *1 | | HA | | 21-2 | 24-21-11 | G00019 | T3 | R | | SM00003 | | GJ | | 155-199, 276-299 |
| 004 | 04 | | HA | | 13-0 | 24-21-11 | G00019 | N | R | | GD05182 | A.. | H7 | | 050-099 |
| 004 | 04 | | HA | | 12-0 | 24-21-11 | G00019 | N | R | | GD05182 | A.. | H7 | | 150-154, 275 |

WIRE LIST

D280T132

91-21-11

Section W0200

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|---------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0204 | 286T0204 | | | FWD TO P31-L1-L GEN POWER FEEDER (continued) | | | | | | | | | | | |
| 004 | 04 | | HA | | 11-9 | 24-21-11 | G00019 | | N | R | | GD05182 | A.. | H7 | 155-199, 276-299 |
| 005 | *2 | | QY | | 62-0 | 24-21-11 | C00901 | | T1 | H* | | SM00001 | | GJ | 050-099 |
| 005 | *2 | | QY | | 72-0 | 24-21-11 | C00901 | | T1 | H* | | SM00001 | | GJ | 150-199, 275-299 |
| 006 | *2 | | QY | | 62-0 | 24-21-11 | C00901 | | T2 | H* | | SM00002 | | GJ | 050-099 |
| 006 | *2 | | QY | | 72-0 | 24-21-11 | C00901 | | T2 | H* | | SM00002 | | GJ | 150-199, 275-299 |
| 007 | *2 | | QY | | 62-0 | 24-21-11 | C00901 | | T3 | H* | | SM00003 | | GJ | 050-099 |
| 007 | *2 | | QY | | 72-0 | 24-21-11 | C00901 | | T3 | H* | | SM00003 | | GJ | 150-199, 275-299 |
| W0205 | 286T0205 | | | POWER DISTRIBUTION RIGHT, P11 TO E1 & E2 | | | | | | | | | | | |
| 001 | 18 | | PA | | 40-0 | SPARE | D04187P | | 40 | | | D04247J | | 15 | ALL |
| 002 | 16 | | PA | | 37-0 | 23-12-21 | D04187P | | 56 | | | D04251J | | 4 | ALL |
| 003 | 22 | | PA | | 33-0 | 27-41-21 | D04187P | | 3 | | | D04257P | | 1 | ALL |
| 004 | 20 | | PA | | 37-0 | SPARE | D04187P | | 4 | | | D04251J | | 3 | ALL |
| 005 | 22 | | PA | | 33-0 | 27-09-11 | D04187P | | 5 | | | D04257P | | 2 | ALL |
| 007 | 22 | | PA | | 33-0 | 27-09-11 | D04187P | | 7 | | | D04257P | | 3 | ALL |
| 009 | 22 | | PA | | 40-0 | 34-22-26 | D04187P | | 9 | | | D04247J | | 9 | ALL |
| 011 | 22 | | PA | | 40-0 | 34-31-21 | D04187P | | 11 | | | D04247J | | 11 | ALL |
| 012 | 20 | | PA | | 40-0 | 27-32-21 | D04187P | | 12 | | | D04247J | | 12 | ALL |
| 013 | 20 | | PA | | 40-0 | 22-11-21 | D04187P | | 13 | | | D04247J | | 13 | ALL |
| 014 | 20 | | PA | | 40-0 | 22-11-22 | D04187P | | 14 | | | D04247J | | 14 | ALL |
| 015 | 20 | | PA | | 40-0 | 22-11-22 | D04187P | | 15 | | | D04247J | | 1 | ALL |
| 016 | 22 | | PA | | 35-0 | 34-51-21 | D04187P | | 16 | | | D04253J | | 4 | ALL |
| 017 | 20 | | PA | | 35-0 | 34-53-21 | D04187P | | 17 | | | D04253J | | 5 | 050-099, 155-199, 275-299 |
| 017 | 22 | | PA | | 35-0 | 34-53-21 | D04187P | | 17 | | | D04253J | | 5 | 150-154 |
| 018 | 22 | | PA | | 35-0 | 34-55-21 | D04187P | | 18 | | | D04253J | | 6 | ALL |
| 019 | 22 | | PA | | 35-0 | 34-12-21 | D04187P | | 19 | | | D04253J | | 7 | ALL |
| 020 | 22 | | PA | | 35-0 | 34-12-21 | D04187P | | 20 | | | D04253J | | 8 | ALL |
| 021 | 22 | | PA | | 35-0 | 34-12-21 | D04187P | | 21 | | | D04253J | | 9 | ALL |
| 022 | 22 | | PA | | 35-0 | 34-12-21 | D04187P | | 22 | | | D04253J | | 10 | ALL |
| 023 | 24 | | PK | | 40-0 | 34-22-26 | D04187P | | 23 | | | D04247J | | 25 | ALL |
| 024 | 24 | | PK | | 40-0 | 27-48-11 | D04187P | | 24 | | | D04247J | | 24 | ALL |
| 025 | 22 | | PA | | 35-0 | 34-61-21 | D04187P | | 25 | | | D04253J | | 12 | ALL |
| 026 | 24 | | PK | | 35-0 | 34-61-21 | D04187P | | 26 | | | D04253J | | 1 | ALL |
| 027 | 24 | | PK | | 35-0 | SPARE | D04187P | | 27 | | | D04253J | | 2 | 150-199, 275-299 |
| 028 | 20 | | PA | | 35-0 | SPARE | D04187P | | 28 | | | D04253J | | 3 | ALL |
| 029 | 20 | | PA | | 37-0 | 23-32-11 | D04187P | | 29 | | | D04251J | | 1 | ALL |
| 030 | 20 | | PA | | 40-0 | 23-26-11 | D04187P | | 8 | | | D04247J | | 3 | ALL |
| 031 | 24 | | PK | | 42-0 | 34-21-21 | D04187P | | 31 | | | D04245J | | 1 | ALL |

WIRE LIST
D280T132

91-21-11
Section W0200
Page 3
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0205 | 286T0205 | | | POWER DISTRIBUTION RIGHT, P11 TO E1 & E2 (continued) | | | | | | | | | | | | |
| 032 | 22 | PA | | 37-0 | 23-71-11 | D04187P | | 32 | | | | D04251J | 2 | | ALL | |
| 033 | 24 | PK | | 40-0 | 31-51-11 | D04187P | | 30 | | | | D04247J | 2 | | ALL | |
| 034 | 20 | PA | | 42-0 | SPARE | D04187P | | 34 | | | | D04245J | 2 | | ALL | |
| 035 | 20 | PA | | 42-0 | SPARE | D04187P | | 35 | | | | D04245J | 3 | | ALL | |
| 036 | 22 | PA | | 33-0 | SPARE | D04187P | | 36 | | | | D04257P | 4 | | ALL | |
| 037 | 22 | PA | | 35-0 | SPARE | D04187P | | 37 | | | | D04253J | 11 | | ALL | |
| 038 | 22 | PA | | 33-0 | SPARE | D04187P | | 38 | | | | D04257P | 5 | | ALL | |
| 039 | 22 | PA | | 35-0 | SPARE | D04187P | | 39 | | | | D04253J | 13 | | ALL | |
| 041 | 24 | PK | | 35-0 | 34-61-26 | D04187P | | 2 | | | | D04253J | 14 | | ALL | |
| W0206 | 286T0206 | | | P32 TO ELEC HYD PUMP 2-R1-115 VAC POWER DISTRIBUTION | | | | | | | | | | | | |
| 004 | 08 | HA | | 3-0 | 29-11-31 | SM00001 | | | GE | | | D00484 | A | | 050-099 | |
| 004 | 08 | HA | | 2-5 | 29-11-31 | SM00001 | | | GE | | | D00484 | A | | 150-199, 275-299 | |
| 005 | 08 | HA | | 3-0 | 29-11-31 | SM00002 | | | GE | | | D00484 | B | | 050-099 | |
| 005 | 08 | HA | | 2-5 | 29-11-31 | SM00002 | | | GE | | | D00484 | B | | 150-199, 275-299 | |
| 006 | 08 | HA | | 3-0 | 29-11-31 | SM00003 | | | GE | | | D00484 | C | | 050-099 | |
| 006 | 08 | HA | | 2-5 | 29-11-31 | SM00003 | | | GE | | | D00484 | C | | 150-199, 275-299 | |
| 011 | 06 | QY | | 80-0 | 29-11-31 | M00898 | | A2 | H6 | | | SM00001 | | GE | 050-099 | |
| 011 | 06 | QY | | 89-6 | 29-11-31 | M00898 | | A2 | H6 | | | SM00001 | | GE | 150-199, 275-299 | |
| 012 | 06 | QY | | 80-0 | 29-11-31 | M00898 | | B2 | H6 | | | SM00002 | | GE | 050-099 | |
| 012 | 06 | QY | | 88-8 | 29-11-31 | M00898 | | B2 | H6 | | | SM00002 | | GE | 150-199, 275-299 | |
| 013 | 06 | QY | | 79-0 | 29-11-31 | M00898 | | C2 | H6 | | | SM00003 | | GE | 050-099 | |
| 013 | 06 | QY | | 88-5 | 29-11-31 | M00898 | | C2 | H6 | | | SM00003 | | GE | 150-199, 275-299 | |
| 016 | 08 | PA | | 11-0 | 24-51-52 | K00102 | | A2 | F | | | SM00007 | | GE | ALL | |
| 017 | 08 | PA | | 10-0 | 24-51-52 | K00102 | | B2 | F | | | SM00008 | | GE | ALL | |
| 018 | 08 | PA | | 9-0 | 24-51-52 | K00102 | | C2 | F | | | SM00009 | | GE | ALL | |
| 022 | 22 | PA | | 49-0 | 27-81-11 | D04422J | | 1 | | | | D04412P | 1 | | 050-099 | |
| 022 | 22 | PA | | 60-0 | 27-81-11 | D04422J | | 1 | | | | D04412P | 1 | | 150-199, 275-299 | |
| 023 | 22 | PA | | 49-0 | 27-81-11 | D04422J | | 2 | | | | D04412P | 2 | | 050-099 | |
| 023 | 22 | PA | | 60-0 | 27-81-11 | D04422J | | 2 | | | | D04412P | 2 | | 150-199, 275-299 | |
| 024 | 22 | PA | | 49-0 | 27-81-11 | D04422J | | 3 | | | | D04412P | 3 | | 050-099 | |
| 024 | 22 | PA | | 60-0 | 27-81-11 | D04422J | | 3 | | | | D04412P | 3 | | 150-199, 275-299 | |
| 025 | 18 | PA | | 13-0 | 27-81-11 | D04422J | | 4 | | | | SP01914 | 9 | | ALL | |
| 026 | 12 | PA | | 90-6 | 27-51-11 | D05322P | | 1 | | | | D05420J | 1 | | ALL | |
| 027 | 12 | PA | | 90-6 | 27-51-11 | D05322P | | 2 | | | | D05420J | 2 | | ALL | |
| 028 | 12 | PA | | 90-6 | 27-51-11 | D05322P | | 3 | | | | D05420J | 3 | | ALL | |
| 029 | 16 | PA | | 5-0 | 27-51-11 | GD00794 | | S.. | 2 | | | D05420J | 8 | | ALL | |
| 030 | 16 | PA | | 5-0 | 27-51-11 | GD00794 | | A.. | 2 | | | D05420J | 5 | | ALL | |
| 031 | 18 | PA | | 5-0 | 27-51-11 | GD00794 | | D.. | 2 | | | D05420J | 6 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0200

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0206 | 286T0206 | | | P32 TO ELEC HYD PUMP 2-R1-115 VAC POWER DISTRIBUTION (continued) | | | | | | | | | | | |
| 032 | 18 | | PA | | 34-0 | 27-51-11 | SP01922 | | | | D05420J | | 7 | | ALL |
| 034 | 08 | | HA | | 3-0 | 29-11-31 | GD03504 | S.. | E* | | D00484 | | D | | 050-099 |
| 034 | 08 | | HA | | 2-3 | 29-11-31 | GD03504 | S.. | E* | | D00484 | | D | | 150-199, 275-299 |
| 035 | 18 | | PA | | 49-0 | SPARE | D04422J | | | 7 | D04412P | | 7 | | 050-099 |
| 035 | 18 | | PA | | 60-0 | SPARE | D04422J | | | 7 | D04412P | | 7 | | 150-199, 275-299 |
| 036 | 18 | | PA | | 71-0 | SPARE | D05420J | | | 4 | D04412P | | 6 | | 050-099 |
| 036 | 18 | | PA | | 84-0 | SPARE | D05420J | | | 4 | D04412P | | 6 | | 150-199, 275-299 |
| 037 | 06 | | QY | | 22-0 | 24-51-52 | SM00009 | | GE | | SM00006 | | | GE | ALL |
| 038 | 06 | | QY | | 22-0 | 24-51-52 | SM00008 | | GE | | SM00005 | | | GE | ALL |
| 039 | 06 | | QY | | 22-0 | 24-51-52 | SM00007 | | GE | | SM00004 | | | GE | ALL |
| 040 | 08 | | PA | | 3-0 | 24-51-52 | D04330P | | A | | SM00004 | | | GE | ALL |
| 041 | 08 | | PA | | 3-0 | 24-51-52 | D04330P | | B | | SM00005 | | | GE | ALL |
| 042 | 08 | | PA | | 3-0 | 24-51-52 | D04330P | | C | | SM00006 | | | GE | ALL |
| W0207 | 286T0207 | | | POWER DISTRIBUTION, P11 TO E1 & P1 | | | | | | | | | | | |
| 001 | 22 | | PA | | 33-0 | SPARE | D04189P | | | 1 | D05325P | | 1 | | ALL |
| 002 | 22 | | PA | | 33-0 | 27-09-11 | D04189P | | | 2 | D05325P | | 2 | | ALL |
| 003 | 22 | | PA | | 33-0 | 27-09-11 | D04189P | | | 3 | D05325P | | 3 | | ALL |
| 004 | 20 | | PA | | 31-0 | 22-31-12 | D04189P | | | 4 | D04239J | | 4 | | ALL |
| 005 | 22 | | PQ | AE | 33-0 | 27-09-11 | D04189P | | | 5 | D05493P | | 2 | | ALL |
| 005Z | | | | AE | 0-0 | 27-09-11 | D04189P | | DED | | D05493P | | DED | | ALL |
| 006 | 22 | | PQ | AF | 33-0 | 27-09-11 | D04189P | | | 6 | D05493P | | 1 | | ALL |
| 006Z | | | | AF | 0-0 | 27-09-11 | D04189P | | DED | | D05493P | | DED | | ALL |
| 007 | 20 | | PA | | 31-0 | 22-11-32 | D04189P | | | 7 | D04241J | | 7 | | ALL |
| 008 | 22 | | PA | | 31-0 | 34-31-31 | D04189P | | | 8 | D04241J | | 8 | | ALL |
| 009 | 20 | | PA | | 31-0 | SPARE | D04189P | | | 9 | D04241J | | 9 | | ALL |
| 010 | 24 | | PK | | 19-0 | 34-22-81 | D04189P | | | 10 | D04267J | | 1 | | ALL |
| 011 | 22 | | PA | | 19-0 | 34-13-11 | D04189P | | | 11 | D04267J | | 2 | | ALL |
| 012 | 20 | | PA | | 19-0 | SPARE | D04189P | | | 12 | D04267J | | 3 | | ALL |
| 013 | 22 | | PA | | 22-0 | 23-51-11 | D04189P | | | 13 | SP00131 | | | 9 | ALL |
| 014 | 20 | | PA | | 22-0 | 27-32-11 | D04189P | | | 14 | SP00221 | | | 9 | ALL |
| 015 | 12 | | PA | | 31-0 | SPARE | D04189P | | | 56 | D04241J | | 14 | | ALL |
| 016 | 24 | | PK | | 31-0 | 34-24-11 | D04189P | | | 16 | D04241J | | 10 | | ALL |
| 017 | 24 | | PK | | 31-0 | 31-51-12 | D04189P | | | 17 | D04241J | | 2 | | ALL |
| 018 | 20 | | PA | | 31-0 | 34-24-11 | D04189P | | | 18 | D04241J | | 11 | | ALL |
| 019 | 18 | | PA | | 33-0 | 27-11-12 | D04189P | | | 40 | D05325P | | 4 | | ALL |
| 021 | 22 | | PA | | 33-0 | SPARE | D04189P | | | 21 | D05493P | | 3 | | ALL |
| 023 | 20 | | PA | | 33-0 | 27-41-31 | D04189P | | | 20 | SP00425 | | | 9 | 050-099, 155-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0200
Page 5
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|--|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0207 | 286T0207 | | | POWER DISTRIBUTION, P11 TO E1 & P1 (continued) | | | | | | | | | | | | | | |
| 024 | 22 | | PA | 31-0 | SPARE | D04189P | | 24 | | | | | D04241J | | 4 | | | ALL |
| 025 | 22 | | PA | 31-0 | SPARE | D04189P | | 25 | | | | | D04241J | | 5 | | | ALL |
| 026 | 22 | | PA | 31-0 | SPARE | D04189P | | 26 | | | | | D04241J | | 6 | | | ALL |
| 028 | 22 | | PA | 31-0 | SPARE | D04189P | | 28 | | | | | D04241J | | 1 | | | ALL |
| 029 | 20 | | PA | 31-0 | SPARE | D04189P | | 29 | | | | | D04239J | | 1 | | | ALL |
| 030 | 20 | | PA | 31-0 | 34-12-11 | D04189P | | 30 | | | | | D04239J | | 2 | | | ALL |
| 032 | 22 | | PA | 31-0 | 34-12-11 | D04189P | | 32 | | | | | D04239J | | 6 | | | ALL |
| 033 | 22 | | PA | 31-0 | 34-12-11 | D04189P | | 33 | | | | | D04239J | | 7 | | | ALL |
| 034 | 22 | | PA | 31-0 | 34-12-11 | D04189P | | 34 | | | | | D04239J | | 8 | | | ALL |
| W0208 | 286T0208 | | | FWD TO P32-R1-R GEN POWER FEEDER | | | | | | | | | | | | | | |
| 001 | *1 | | HA | 19-0 | 24-21-21 | G00019 | | T1 | R | | | | SM00001 | | GJ | | | 050-099, 150-154, 162-163, 275-276 |
| 001 | *1 | | HA | 18-0 | 24-21-21 | G00019 | | T1 | R | | | | SM00001 | | GJ | | | 155-157, 164-199, 277-299 |
| 002 | *1 | | HA | 19-0 | 24-21-21 | G00019 | | T2 | R | | | | SM00002 | | GJ | | | 050-099, 150-154, 162-163, 275-276 |
| 002 | *1 | | HA | 18-0 | 24-21-21 | G00019 | | T2 | R | | | | SM00002 | | GJ | | | 155-157, 164-199, 277-299 |
| 003 | *1 | | HA | 19-0 | 24-21-21 | G00019 | | T3 | R | | | | SM00003 | | GJ | | | 050-099, 150-154, 162-163, 275-276 |
| 003 | *1 | | HA | 18-0 | 24-21-21 | G00019 | | T3 | R | | | | SM00003 | | GJ | | | 155-157, 164-199, 277-299 |
| 004 | 04 | | HA | 13-0 | 24-21-21 | G00019 | | N | R | | | | GD05248 | A.. | H7 | | | 050-099, 150-154, 162-163, 275-276 |
| 004 | 04 | | HA | 12-0 | 24-21-21 | G00019 | | N | R | | | | GD05248 | A.. | H7 | | | 155-157, 164-199, 277-299 |
| 005 | *2 | | QY | 62-0 | 24-21-21 | C00903 | | T1 | H* | | | | SM00001 | | GJ | | | 050-099 |
| 005 | *2 | | QY | 72-0 | 24-21-21 | C00903 | | T1 | H* | | | | SM00001 | | GJ | | | 150-154, 275 |
| 005 | *2 | | QY | 78-0 | 24-21-21 | C00903 | | T1 | H* | | | | SM00001 | | GJ | | | 155-157, 164-199, 277-278 |
| 005 | *2 | 43 | | 72-0 | 24-21-21 | C00903 | | T1 | H* | | | | SM00001 | | GJ | | | 162-163, 276 |
| 005 | *2 | QY | | 79-0 | 24-21-21 | C00903 | | T1 | H* | | | | SM00001 | | GJ | | | 280-299 |
| 006 | *2 | QY | | 62-0 | 24-21-21 | C00903 | | T2 | H* | | | | SM00002 | | GJ | | | 050-099 |
| 006 | *2 | QY | | 72-0 | 24-21-21 | C00903 | | T2 | H* | | | | SM00002 | | GJ | | | 150-154, 275 |
| 006 | *2 | QY | | 78-0 | 24-21-21 | C00903 | | T2 | H* | | | | SM00002 | | GJ | | | 155-157, 164-199, 277-278 |
| 006 | *2 | 43 | | 72-0 | 24-21-21 | C00903 | | T2 | H* | | | | SM00002 | | GJ | | | 162-163, 276 |
| 006 | *2 | QY | | 79-0 | 24-21-21 | C00903 | | T2 | H* | | | | SM00002 | | GJ | | | 280-299 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0208 | 286T0208 | | | FWD TO P32-R1-R GEN POWER FEEDER (continued) | | | | | | | | | | | |
| 007 | *2 | | QY | | 62-0 | 24-21-21 | C00903 | T3 | H* | | SM00003 | | GJ | | 050-099 |
| 007 | *2 | | QY | | 72-0 | 24-21-21 | C00903 | T3 | H* | | SM00003 | | GJ | | 150-154, 275 |
| 007 | *2 | | QY | | 78-0 | 24-21-21 | C00903 | T3 | H* | | SM00003 | | GJ | | 155-157, 164-199, 277-278 |
| 007 | *2 | | 43 | | 72-0 | 24-21-21 | C00903 | T3 | H* | | SM00003 | | GJ | | 162-163, 276 |
| 007 | *2 | | QY | | 79-0 | 24-21-21 | C00903 | T3 | H* | | SM00003 | | GJ | | 280-299 |
| W0209 | 286T0209 | | | POWER DISTRIBUTION LEFT, P11 TO P1 | | | | | | | | | | | |
| 001 | 22 | | PA | | 19-0 | 34-22-82 | D04165P | | | 1 | D04163J | | | 1 | ALL |
| 002 | 22 | | PA | | 19-0 | 31-41-11 | D04165P | | | 2 | D04163J | | | 2 | ALL |
| 003 | 24 | | PK | | 19-0 | 34-22-16 | D04165P | | | 3 | D04163J | | | 3 | ALL |
| 004 | 24 | | PK | | 19-0 | 34-22-16 | D04165P | | | 4 | D04163J | | | 4 | ALL |
| 005 | 22 | | PA | | 19-0 | 34-13-11 | D04165P | | | 5 | D04163J | | | 5 | ALL |
| 006 | 22 | | PA | | 19-0 | 34-13-11 | D04165P | | | 6 | D04163J | | | 6 | ALL |
| 007 | 24 | | PK | | 19-0 | 31-25-11 | D04165P | | | 7 | D04163J | | | 7 | ALL |
| 008 | 24 | | PK | | 19-0 | 34-22-16 | D04165P | | | 8 | D04163J | | | 8 | ALL |
| 009 | 22 | | PA | | 19-0 | 29-21-32 | D04165P | | | 9 | D04163J | | | 9 | ALL |
| 010 | 22 | | PA | | 19-0 | SPARE | D04165P | | | 10 | D04163J | | | 10 | ALL |
| 011 | 22 | | PA | | 19-0 | SPARE | D04165P | | | 11 | D04163J | | | 11 | ALL |
| 012 | 20 | | PA | | 19-0 | 34-43-12 | D04165P | | | 12 | SP00003 | | | 9 | ALL |
| 019 | 24 | | PK | | 19-0 | 34-61-15 | D04165P | | | 19 | D04163J | | | 13 | 050-099 |
| 019 | 24 | | PK | | 19-0 | SPARE | D04165P | | | 19 | D04163J | | | 13 | 150-199 |
| 025 | 22 | | PA | | 19-0 | SPARE | D04165P | | | 25 | D04163J | | | 15 | 150-199 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0210 | 286T0210 | | | P6 TO P31-L1-LEFT GEN POWER FEEDER | | | | | | | | | | | | |
| 001 | 04 | | QY | 30-0 | 24-51-11 | C00901 | L1 | H4 | | TB5002 | 1 | F4 | | ALL | | |
| 002 | 04 | | QY | 30-0 | 24-51-11 | C00901 | L2 | H4 | | TB5002 | 2 | F4 | | ALL | | |
| 003 | 04 | | QY | 30-0 | 24-51-11 | C00901 | L3 | H4 | | TB5002 | 3 | F4 | | ALL | | |
| 03P | 08 | | PA | 27-0 | 24-54-11 | TB5130 | 7 | E | | TB5010 | 5 | F | | 050-099, 155-157, 164-199, 277-299 | | |
| 03P | 08 | | PA | 27-0 | 24-54-11 | TB5130 | 7 | C | | TB5010 | 5 | F | | 150-154, 162-163, 275-276 | | |
| W0211 | 286T0211 | | | POWER DISTRIBUTION RIGHT, P11 TO E1, E2, E5 & P3 | | | | | | | | | | | | |
| 001 | 20 | | PA | 36-0 | 23-11-21 | D04193P | 1 | | | D04255J | 1 | | | ALL | | |
| 002 | 20 | | PA | 36-0 | 23-11-21 | D04193P | 2 | | | D04255J | 2 | | | ALL | | |
| 003 | 20 | | PA | 36-0 | 23-11-21 | D04193P | 3 | | | D04255J | 3 | | | ALL | | |
| 004 | 22 | | PA | 23-0 | 31-41-11 | D04193P | 4 | | | D04263J | 10 | | | ALL | | |
| 005 | 20 | | PA | 36-0 | SPARE | D04193P | 5 | | | D04255J | 5 | | | ALL | | |
| 006 | 20 | | PA | 23-0 | SPARE | D04193P | 6 | | | D04263J | 6 | | | ALL | | |
| 007 | 20 | | PA | 2-0 | 23-11-21 | GD00529 | A.. | E | | D04255J | 8 | | | ALL | | |
| 008 | 24 | | PK | 23-0 | 34-22-91 | D04193P | 8 | | | D04263J | 8 | | | ALL | | |
| 009 | 22 | | PA | 23-0 | 34-22-92 | D04193P | 9 | | | D04263J | 11 | | | ALL | | |
| 010 | 24 | | PK | 23-0 | 34-22-26 | D04193P | 10 | | | D04263J | 4 | | | ALL | | |
| 011 | 24 | | PK | 23-0 | 34-22-26 | D04193P | 11 | | | D04263J | 3 | | | ALL | | |
| 012 | 24 | | PK | 23-0 | 34-22-26 | D04193P | 12 | | | D04263J | 9 | | | ALL | | |
| 013 | 22 | | PA | 23-0 | 34-13-21 | D04193P | 13 | | | D04263J | 13 | | | ALL | | |
| 014 | 22 | | PA | 23-0 | 34-13-21 | D04193P | 14 | | | D04263J | 15 | | | ALL | | |
| 016 | 24 | | PK | 23-0 | 31-25-11 | D04193P | 16 | | | D04263J | 19 | | | ALL | | |
| 017 | 22 | | PA | 23-0 | SPARE | D04193P | 17 | | | D04263J | 17 | | | ALL | | |
| 018 | 22 | | PA | 59-0 | 34-33-21 | D04193P | 18 | | | D04259J | 1 | | | ALL | | |
| 019 | 22 | | PA | 23-0 | SPARE | D04193P | 31 | | | D04263J | 21 | | | 150-199 | | |
| 020 | 20 | | PA | 59-0 | SPARE | D04193P | 20 | | | D04259J | 2 | | | ALL | | |
| 021 | 20 | | PA | 59-0 | SPARE | D04193P | 21 | | | D04259J | 3 | | | ALL | | |
| 022 | 22 | | PA | 23-0 | 31-41-11 | D04193P | 22 | | | D04263J | 12 | | | ALL | | |
| 023 | 24 | | PK | 9-0 | 31-51-12 | D04193P | 7 | | | SP00039 | | 9 | | ALL | | |
| 025 | 20 | | PA | 59-0 | SPARE | D04193P | 25 | | | D04259J | 6 | | | ALL | | |
| 026 | 22 | | PA | 59-0 | SPARE | D04193P | 26 | | | D04259J | 8 | | | ALL | | |
| 028 | 20 | | PA | 19-0 | 34-43-22 | D04193P | 28 | | | SP00007 | | 9 | | ALL | | |
| 029 | 24 | | PK | 23-0 | 34-61-25 | D04193P | 23 | | | D04263J | 1 | | | 050-099 | | |
| 029 | 24 | | PK | 23-0 | SPARE | D04193P | 23 | | | D04263J | 1 | | | 150-199, 275-299 | | |
| 040 | 16 | | PA | 23-0 | SPARE | D04193P | 40 | | | D04263J | 14 | | | ALL | | |
| 056 | 18 | | PA | 59-0 | SPARE | D04193P | 56 | | | D04259J | 4 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0210

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0212 | 286T0212 | | | P6 TO P32-R1-R GEN PWR FEEDER | | | | | | | | | | | |
| 001 | 06 | | QY | | 29-6 | 24-51-21 | C00903 | L1 | H6 | | TB5008 | 1 | E/ | | ALL |
| 002 | 06 | | QY | | 29-6 | 24-51-21 | C00903 | L2 | H6 | | TB5008 | 2 | E/ | | ALL |
| 003 | 06 | | QY | | 29-6 | 24-51-21 | C00903 | L3 | H6 | | TB5008 | 3 | E/ | | ALL |
| W0214 | 286T0214 | | | P4 TO L WING FS/BODY-L2-LEFT IDG CONT | | | | | | | | | | | |
| 001 | 24 | | PK | | 43-7 | 24-11-11 | D04058J | | | 16 | D04550J | | | | 050-099 |
| 001 | 24 | | PK | | 54-4 | 24-11-11 | D04058J | | | 16 | D04550J | | | | 150-199, 275-299 |
| 003 | 24 | | PK | | 24-1 | 24-22-12 | D04110J | | | 1 | D04054P | | | | ALL |
| 004 | 24 | | PK | | 24-1 | 24-22-12 | D04110J | | | 2 | D04054P | | | | ALL |
| 005 | 24 | | PK | | 24-1 | 24-51-13 | D04110J | | | 3 | D04054P | | | | ALL |
| 006 | 24 | | PK | | 15-4 | 24-11-11 | D04058J | | | 22 | D06232P | A03 | \$D | | ALL |
| 007 | 24 | | PK | | 15-4 | 30-41-11 | D04058J | | | 23 | D06232P | A06 | \$D | | ALL |
| 008 | 24 | | PK | | 32-0 | 24-11-11 | D04058J | | | 24 | D04778P | | | 9 | ALL |
| 009 | 24 | | PK | | 32-0 | 24-11-11 | D04058J | | | 25 | D04778P | | | 10 | ALL |
| 010 | 24 | | PK | | 32-0 | 24-22-11 | D04058J | | | 26 | D04778P | | | 11 | ALL |
| 011 | 24 | | PK | | 32-0 | 24-22-11 | D04058J | | | 27 | D04778P | | | 12 | ALL |
| 012 | 24 | | PK | | 32-0 | 24-22-11 | D04058J | | | 28 | D04778P | | | 42 | ALL |
| 013 | 24 | | PK | | 32-0 | 24-22-12 | D04058J | | | 29 | D04778P | | | 14 | ALL |
| 014 | 24 | | PK | | 15-4 | 24-27-11 | D04058J | | | 30 | D06232P | A10 | \$D | | ALL |
| 015 | 24 | | PK | | 15-4 | 30-41-11 | D04058J | | | 31 | D06232P | A07 | \$D | | ALL |
| 016 | 24 | | PK | | 32-0 | 24-11-11 | D04058J | | | 32 | D04778P | | | 17 | ALL |
| 017 | 20 | | PA | | 32-0 | 24-22-11 | D04058J | | | 33 | D04778P | | | 18 | ALL |
| 018 | 20 | | PA | | 32-0 | 24-22-11 | D04058J | | | 34 | D04778P | | | 19 | ALL |
| 019 | 24 | | PK | | 32-0 | 24-22-12 | D04058J | | | 35 | D04778P | | | 20 | ALL |
| 020 | 18 | | PA | | 17-7 | 24-22-11 | D04060J | | | 7 | D04080P | | 4 | DL | ALL |
| 021 | 18 | | PA | | 17-7 | 24-22-12 | D04060J | | | 8 | D04080P | | 5 | DL | ALL |
| 023 | 20 | | PA | | 17-4 | 25-31-21 | D04058J | | | 48 | D04080P | | 21 | | 050-099, 150-199 |
| 023 | 18 | | PA | | 17-4 | 25-31-21 | D04058J | | DK | 48 | D04080P | | 21 | | 275-299 |
| 024 | 20 | | PA | | 27-2 | SPARE | D04110J | | | 4 | D04776P | | | 3 | ALL |
| 025 | 22 | | PA | | 27-2 | 25-31-21 | D04110J | | | 5 | D04776P | | | 4 | ALL |
| 027 | 22 | | PA | | 24-1 | 25-31-21 | D04110J | | | 7 | D04080P | | | 9 | ALL |
| 028 | 24 | | PK | | 17-4 | 24-22-11 | D04058J | | | 36 | D04054P | | | 4 | ALL |
| 029 | 24 | | PK | | 17-4 | 24-22-12 | D04058J | | | 37 | D04054P | | | 5 | ALL |
| 030 | 24 | | PK | | 40-1 | 24-51-71 | D04778P | | | 47 | D04080P | | | 20 | ALL |
| 032 | 24 | | PK | | 26-7 | 24-27-11 | D04080P | | | 16 | D06232P | A08 | \$D | | ALL |
| 033 | 24 | | PK | | 26-7 | 24-27-11 | D04080P | | | 17 | D06232P | A09 | \$D | | ALL |
| 034 | 24 | | PK | | 26-8 | 24-28-11 | D04054P | | | 18 | D06232P | A04 | \$D | | ALL |
| 035 | 24 | | PK | | 40-1 | 24-51-13 | D04054P | | | 19 | D04778P | | | 25 | ALL |
| 036 | 24 | | PK | | 40-1 | 24-51-13 | D04054P | | | 20 | D04778P | | | 26 | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0210
 Page 2
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0214 | 286T0214 | | | P4 TO L WING FS/BODY-L2-LEFT IDG CONT (continued) | | | | | | | | | | | |
| 037 | 24 | | PK | 27-3 | 24-51-71 | D04778P | | 43 | | | D04110J | | 31 | | ALL |
| 038 | 24 | | PK | 27-3 | 24-51-71 | D04778P | | 44 | | | D04110J | | 19 | | ALL |
| 039 | 24 | | PK | 27-3 | 24-51-71 | D04778P | | 45 | | | D04110J | | 35 | | ALL |
| 040 | 24 | | PK | 40-1 | 24-51-71 | D04778P | | 46 | | | D04080P | | 24 | | ALL |
| 041 | 20 | | PA | 17-8 | 24-22-11 | D04060J | | 9 | | | D04054P | | 21 | | ALL |
| 042 | 20 | | PA | 17-8 | 24-22-11 | D04060J | | 10 | | | D04054P | | 22 | | ALL |
| 043 | 20 | | PA | 17-8 | 24-22-11 | D04060J | | 11 | | | D04054P | | 23 | | ALL |
| 044 | 20 | | PA | 17-8 | 24-22-12 | D04060J | | 12 | | | D04054P | | 24 | | ALL |
| 045 | 20 | | PA | 17-8 | 24-22-12 | D04060J | | 13 | | | D04054P | | 25 | | ALL |
| 046 | 20 | | PA | 17-8 | 24-22-12 | D04060J | | 14 | | | D04054P | | 26 | | ALL |
| 047 | 18 | | PQ | Q | 43-8 | 24-11-11 | D04060J | | 15 | | D04398J | | 4 | | 050-099 |
| 047 | 18 | | PQ | Q | 54-10 | 24-11-11 | D04060J | | 15 | | D04398J | | 4 | | 150-199, 275-299 |
| 047Z | | | | Q | 0-0 | 24-11-11 | D04060J | DED | | | D04398J | DED | | | ALL |
| 048 | 24 | | PK | | 24-1 | 24-27-21 | D04110J | | 15 | | D04054P | | 27 | | ALL |
| 049 | 24 | | PK | | 24-1 | 24-27-21 | D04110J | | 16 | | D04054P | | 28 | | ALL |
| 050 | 24 | | PK | | 24-1 | 24-27-11 | D04110J | | 17 | | D04080P | | 29 | | ALL |
| 056 | 24 | | PK | | 24-1 | 29-11-22 | D04054P | | 32 | | D04110J | | 18 | | ALL |
| 061 | 24 | | PV | AA | 40-1 | 29-11-31 | D04054P | | 37 | | D04778P | | 32 | | ALL |
| 061Z | | | | AA | 0-0 | 29-11-31 | D04054P | DED | | | D04778P | DED | | | ALL |
| 062 | 22 | | PA | | 40-1 | 29-32-11 | D04054P | | 38 | | D04778P | | 33 | | ALL |
| 063 | 22 | | PQ | R | 27-3 | 29-11-31 | D04110J | | 14 | | D04778P | | 34 | | ALL |
| 063Z | | | | R | 0-0 | 29-11-31 | D04110J | DED | | | D04778P | DED | | | ALL |
| 064 | 24 | | PV | AB | 24-1 | 31-31-26 | D04080P | | 18 | | D04110J | | 38 | | ALL |
| 064Z | | | | AB | 0-0 | 31-31-26 | D04080P | DED | | | D04110J | DED | | | ALL |
| 065 | 22 | | PA | | 77-2 | 24-11-11 | D04550J | | 22 | | D04778P | | 36 | | 150-199 |
| 066 | 24 | | PK | | 24-1 | 24-22-11 | D04110J | | 20 | | D04054P | | 40 | | ALL |
| 067 | 24 | | PK | | 24-1 | 24-51-31 | D04110J | | 21 | | D04054P | | 41 | | ALL |
| 068 | 20 | | PA | | 24-1 | 24-22-12 | D04110J | | 22 | | D04054P | | 42 | | ALL |
| 069 | 24 | | PK | | 24-1 | 24-51-31 | D04110J | | 23 | | D04054P | | 43 | | ALL |
| 070 | 24 | | PK | | 24-1 | 24-22-12 | D04110J | | 24 | | D04054P | | 44 | | ALL |
| 071 | 24 | | PK | | 24-1 | 24-51-31 | D04110J | | 25 | | D04054P | | 45 | | ALL |
| 072 | 20 | | PA | | 24-1 | 24-22-12 | D04110J | | 26 | | D04054P | | 46 | | ALL |
| 073 | 24 | | PK | | 24-1 | 24-51-31 | D04110J | | 27 | | D04054P | | 47 | | ALL |
| 074 | 20 | | PA | | 24-1 | 24-22-22 | D04110J | | 28 | | D04054P | | 48 | | ALL |
| 075 | 20 | | PA | | 24-1 | 24-22-22 | D04110J | | 29 | | D04054P | | 49 | | ALL |
| 076 | 24 | | PK | | 16-0 | 24-22-12 | D04110J | | 30 | | D04058J | | 55 | | ALL |
| 077 | 24 | | PV | S | 24-1 | 29-11-31 | D04054P | | 50 | | D04110J | | 32 | | ALL |
| 077Z | | | | S | 0-0 | 29-11-31 | D04054P | DED | | | D04110J | DED | | | ALL |
| 078 | 24 | | PV | T | 24-1 | 29-11-31 | D04054P | | 51 | | D04110J | | 33 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0210

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0214 | 286T0214 | | | P4 TO L WING FS/BODY-L2-LEFT IDG CONT (continued) | | | | | | | | | | | |
| 078Z | | | | T | 0-0 | 29-11-31 | D04054P | | DED | | D04110J | | DED | | ALL |
| 079 | 24 | | PV | U | 24-1 | 29-11-31 | D04054P | | 52 | | D04110J | | 34 | | ALL |
| 079Z | | | | U | 0-0 | 29-11-31 | D04054P | | DED | | D04110J | | DED | | ALL |
| 081 | 22 | | PQ | AC | 40-1 | 29-11-31 | D04054P | | 34 | | D04778P | | 39 | | ALL |
| 081Z | | | | AC | 0-0 | 29-11-31 | D04054P | | DED | | D04778P | | DED | | ALL |
| 082 | 24 | | PK | | 32-4 | 24-11-11 | D04778P | | 37 | | D04060J | | 16 | | 150-199 |
| 083 | 24 | | PK | | 40-1 | 24-51-31 | D04080P | | 12 | | D04778P | | 40 | | ALL |
| 084 | 24 | | PK | | 40-1 | 24-51-31 | D04080P | | 13 | | D04778P | | 16 | | ALL |
| 087 | 24 | | PK | | 24-1 | 31-31-26 | D04080P | | 19 | | D04110J | | 39 | | ALL |
| 089 | 20 | | PA | | 40-1 | 24-51-72 | D04778P | | 48 | | D04080P | | 38 | | 050-099 |
| 089 | 20 | | PA | | 40-1 | SPARE | D04080P | | 38 | | D04778P | | 48 | | 155-157, 165-199, 277-299 |
| 089 | 20 | | PA | | 40-1 | 24-51-72 | D04080P | | 38 | | D04778P | | 48 | | 162-164, 276 |
| 090 | 20 | | PA | | 40-1 | 24-51-72 | D04080P | | 39 | | D04778P | | 49 | | 050-099, 162-164, 276 |
| 090 | 20 | | PA | | 40-1 | SPARE | D04080P | | 39 | | D04778P | | 49 | | 155-157, 165-199, 277-299 |
| 102 | 20 | | PA | | 50-5 | SPARE | D04550J | | 18 | | D04110J | | 41 | | 050-099 |
| 102 | 20 | | PA | | 61-2 | SPARE | D04550J | | 18 | | D04110J | | 41 | | 150-199, 275-299 |
| 103 | 20 | | PA | | 66-10 | SPARE | D04550J | | 19 | | D04778P | | 35 | | 050-099 |
| 103 | 20 | | PA | | 77-2 | SPARE | D04550J | | 19 | | D04778P | | 35 | | 150-199, 275-299 |
| 107 | 24 | | PK | | 24-1 | 29-11-22 | D04054P | | 14 | | D04110J | | 8 | | ALL |
| 108 | 24 | | PV | V | 24-1 | 29-11-31 | D04080P | | 14 | | D04110J | | 13 | | ALL |
| 108Z | | | | V | 0-0 | 29-11-31 | D04080P | | DED | | D04110J | | DED | | ALL |
| 109 | 24 | | PK | | 40-1 | 24-22-12 | D04778P | | 7 | | D04054P | | 54 | | ALL |
| 110 | 24 | | PK | | 32-0 | 24-22-11 | D04058J | | 17 | | D04778P | | 2 | | ALL |
| 111 | 24 | | PK | | 15-4 | 24-28-21 | D04058J | | 4 | | D06232P | | A05 | \$D | ALL |
| 112 | 24 | | PK | | 15-4 | 24-11-11 | D06232P | | A02 | \$D | D04058J | | 53 | | ALL |
| 113 | 24 | | PK | | 27-3 | 24-11-11 | D04778P | | 8 | | D04110J | | 9 | | ALL |
| 118 | 24 | | PK | | 22-0 | 24-11-11 | D04058J | | 54 | | D06232P | | A12 | \$D | 050-099 |
| 118 | 24 | | PK | | 22-0 | 24-11-11 | D06232P | | A12 | \$D | D04058J | | 54 | | 150-199, 275-299 |
| 119 | 24 | | PK | | 1-3 | SPARE | D06232P | | CAP | Y | D06232P | | A13 | \$D | ALL |
| 120 | 24 | | PK | | 1-3 | SPARE | D06232P | | CAP | Y | D06232P | | A14 | \$D | ALL |
| 121 | 24 | | PK | | 1-3 | SPARE | D06232P | | CAP | Y | D06232P | | A15 | \$D | ALL |
| 122 | 24 | | PK | | 1-3 | SPARE | D06232P | | CAP | Y | D06232P | | A16 | \$D | ALL |
| 123 | 24 | | PK | | 1-3 | SPARE | D06232P | | CAP | Y | D06232P | | A17 | \$D | ALL |
| 124 | 24 | | PK | | 1-3 | SPARE | D06232P | | CAP | Y | D06232P | | A18 | \$D | ALL |
| 125 | 24 | | PK | | 1-3 | SPARE | D06232P | | CAP | Y | D06232P | | A19 | \$D | ALL |
| 126 | 24 | | PK | | 40-1 | 24-27-11 | D04778P | | 21 | | D04080P | | 26 | | ALL |
| 127 | 24 | | PK | | 40-1 | 24-27-11 | D04778P | | 22 | | D04080P | | 25 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0210

Page 4

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0214 | 286T0214 | | | P4 TO L WING FS/BODY-L2-LEFT IDG CONT (continued) | | | | | | | | | | | | | |
| 128 | 24 | | PK | 32-0 | 24-27-11 | D04778P | | 23 | | | | | D04058J | 52 | | | ALL |
| 129 | 16 | | PA | 40-1 | 25-31-21 | D04778P | | 13 | FL | | | | D04080P | 23 | | | 050-099, 150-199 |
| 129 | 16 | | PA | 40-0 | 25-31-21 | D04776P | | 1 | | | | | D04080P | 23 | | | 275-299 |
| 140 | 20 | | PA | 66-10 | SPARE | D04550J | | 20 | | | | | D04778P | 41 | | | 050-099 |
| 140 | 20 | | PA | 77-2 | SPARE | D04550J | | 20 | | | | | D04778P | 41 | | | 150-199, 275-299 |
| 141 | 24 | | PK | 15-4 | 24-11-11 | D06232P | | A11 | \$D | | | | D04058J | 47 | | | ALL |
| 142 | 24 | | PK | 24-1 | 29-11-22 | D04110J | | 37 | | | | | D04054P | 16 | | | ALL |
| 143 | 16 | | PA | 40-1 | 25-31-31 | D04778P | | 1 | FL | | | | D04080P | 30 | FL | | 277-299 |
| 145 | 18 | | PA | 17-4 | 25-31-31 | D04058J | | 46 | DK | | | | D04080P | 32 | DL | | 277-299 |
| 201B | 24 | | PW | A | 43-7 | 24-11-11 | D04058J | 1 | | | | | D04550J | 1 | | | 050-099 |
| 201B | 24 | | PW | A | 54-4 | 24-11-11 | D04058J | 1 | | | | | D04550J | 1 | | | 150-199, 275-299 |
| 201R | 24 | | PW | A | 0-0 | 24-11-11 | D04058J | 2 | | | | | D04550J | 2 | | | ALL |
| 201Z | | | | A | 0-0 | 24-11-11 | D04058J | 3 | | | | | D04550J | 3 | | | ALL |
| 202B | 24 | | PL | B | 43-7 | 24-11-11 | D04058J | 12 | | | | | D04550J | 12 | | | 050-099 |
| 202B | 24 | | PL | B | 54-4 | 24-11-11 | D04058J | 12 | | | | | D04550J | 12 | | | 150-199, 275-299 |
| 202R | 24 | | PL | B | 0-0 | 24-11-11 | D04058J | 13 | | | | | D04550J | 13 | | | ALL |
| 203B | 24 | | PL | C | 43-7 | 24-11-11 | D04058J | 14 | | | | | D04550J | 14 | | | 050-099 |
| 203B | 24 | | PL | C | 54-4 | 24-11-11 | D04058J | 14 | | | | | D04550J | 14 | | | 150-199, 275-299 |
| 203R | 24 | | PL | C | 0-0 | 24-11-11 | D04058J | 15 | | | | | D04550J | 15 | | | ALL |
| 204B | 20 | | PR | E | 43-7 | 24-21-11 | D04058J | 5 | | | | | D04550J | 5 | | | 050-099 |
| 204B | 20 | | PR | E | 54-4 | 24-21-11 | D04058J | 5 | | | | | D04550J | 5 | | | 150-199, 275-299 |
| 204R | 20 | | PR | E | 0-0 | 24-21-11 | D04058J | 6 | | | | | D04550J | 6 | | | ALL |
| 204Z | | | | E | 0-0 | 24-21-11 | D04058J | 7 | | | | | D04550J | 7 | | | ALL |
| 206B | 24 | | PW | J | 16-0 | 24-22-12 | D04058J | 49 | | | | | D04110J | 10 | | | ALL |
| 206R | 24 | | PW | J | 0-0 | 24-22-12 | D04058J | 50 | | | | | D04110J | 11 | | | ALL |
| 206Z | | | | J | 0-0 | 24-22-12 | D04058J | 51 | | | | | D04110J | 12 | | | ALL |
| 301B | 18 | | PC | K | 43-8 | 24-21-11 | D04060J | 1 | | | | | D04398J | 1 | | | 050-099 |
| 301B | 18 | | PC | K | 54-10 | 24-21-11 | D04060J | 1 | | | | | D04398J | 1 | | | 150-199, 275-299 |
| 301R | 18 | | PC | K | 0-0 | 24-21-11 | D04060J | 2 | | | | | D04398J | 2 | | | ALL |
| 301Y | 18 | | PC | K | 0-0 | 24-21-11 | D04060J | 3 | | | | | D04398J | 3 | | | ALL |
| 302B | 18 | | PC | L | 17-7 | 24-21-11 | D04060J | 4 | | | | | D04080P | 1 | DL | | ALL |
| 302R | 18 | | PC | L | 0-0 | 24-21-11 | D04060J | 5 | | | | | D04080P | 2 | DL | | ALL |
| 302Y | 18 | | PC | L | 0-0 | 24-21-11 | D04060J | 6 | | | | | D04080P | 3 | DL | | ALL |
| 401B | 24 | | PN | D | 43-7 | 24-21-11 | D04058J | 8 | | | | | D04550J | 8 | | | 050-099 |
| 401B | 24 | | PN | D | 54-4 | 24-21-11 | D04058J | 8 | | | | | D04550J | 8 | | | 150-199, 275-299 |
| 401G | 24 | | PN | D | 0-0 | 24-21-11 | D04058J | 11 | | | | | D04550J | 11 | | | ALL |
| 401R | 24 | | PN | D | 0-0 | 24-21-11 | D04058J | 9 | | | | | D04550J | 9 | | | ALL |
| 401Y | 24 | | PN | D | 0-0 | 24-21-11 | D04058J | 10 | | | | | D04550J | 10 | | | ALL |
| 402B | 24 | | PN | G | 32-0 | 24-23-11 | D04058J | 18 | | | | | D04778P | 3 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0210

Page 5

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0214 | 286T0214 | | | P4 TO L WING FS/BODY-L2-LEFT IDG CONT (continued) | | | | | | | | | | | |
| 402G | 24 | PN | G | | 0-0 | 24-23-11 | D04058J | | 19 | | D04778P | | 4 | | ALL |
| 402R | 24 | PN | G | | 0-0 | 24-23-11 | D04058J | | 20 | | D04778P | | 5 | | ALL |
| 402Y | 24 | PN | G | | 0-0 | 24-23-11 | D04058J | | 21 | | D04778P | | 6 | | ALL |
| 403B | 24 | PN | H | | 17-4 | 24-23-11 | D04058J | | 38 | | D04054P | | 6 | | ALL |
| 403G | 24 | PN | H | | 0-0 | 24-23-11 | D04058J | | 39 | | D04054P | | 7 | | ALL |
| 403R | 24 | PN | H | | 0-0 | 24-23-11 | D04058J | | 40 | | D04054P | | 8 | | ALL |
| 403Y | 24 | PN | H | | 0-0 | 24-23-11 | D04058J | | 41 | | D04054P | | 9 | | ALL |
| 404B | 24 | PN | I | | 17-4 | 24-23-11 | D04058J | | 42 | | D04054P | | 10 | | ALL |
| 404G | 24 | PN | I | | 0-0 | 24-23-11 | D04058J | | 43 | | D04054P | | 11 | | ALL |
| 404R | 24 | PN | I | | 0-0 | 24-23-11 | D04058J | | 44 | | D04054P | | 12 | | ALL |
| 404Y | 24 | PN | I | | 0-0 | 24-23-11 | D04058J | | 45 | | D04054P | | 13 | | ALL |
| W0216 | 286T0216 | | | P31 TO A2-L2-L DISC. AFT GALLEY CONTROL | | | | | | | | | | | |
| 001 | 20 | PA | | | 35-0 | 25-31-21 | D11840 | | 4 | | D12098 | | 4 | | 275-299 |
| 002 | 18 | PA | | | 19-0 | 33-51-13 | D00592 | | 1 | DK | SP00648 | | | S | 275-299 |
| 003 | 18 | PA | | | 3-0 | 33-51-13 | D00592 | | 2 | DK | GD02570 | | D.. | E | 275-299 |
| 004 | 24 | PK | | | 133-0 | 25-31-21 | SM00012 | | | S | D04068P | | 8 | | 050-099 |
| 004 | 24 | PK | | | 2-0 | 25-31-21 | D04068P | | 8 | | SM00012 | | | S | 150-199 |
| 004 | 24 | PK | | | 156-0 | 25-31-21 | D00592 | | 4 | | D04068P | | 8 | | 275-299 |
| 005 | 24 | PK | | | 133-0 | 25-31-21 | SM00010 | | | S | D04068P | | 5 | | 050-099 |
| 005 | 24 | PK | | | 2-0 | 25-31-21 | SM00010 | | | S | D04068P | | 5 | | 150-199 |
| 005 | 24 | PK | | | 156-0 | 25-31-21 | D00592 | | 5 | | D04068P | | 5 | | 275-299 |
| 006 | 24 | PK | | | 133-0 | 25-31-21 | SM00008 | | | S | D04068P | | 6 | | 050-099 |
| 006 | 24 | PK | | | 2-0 | 25-31-21 | SM00008 | | | S | D04068P | | 6 | | 150-199 |
| 006 | 24 | PK | | | 156-0 | 25-31-21 | D00592 | | 6 | | D04068P | | 6 | | 275-299 |
| 007 | 24 | PK | | | 133-0 | 25-31-21 | SM00006 | | | S | D04068P | | 9 | | 050-099 |
| 007 | 24 | PK | | | 2-0 | 25-31-21 | SM00006 | | | S | D04068P | | 9 | | 150-199 |
| 007 | 24 | PK | | | 156-0 | 25-31-21 | D00592 | | 7 | | D04068P | | 9 | | 275-299 |
| 008 | 20 | PA | | | 3-0 | 25-31-21 | D00592 | | 9 | | GD02570 | | D.. | E | 050-099, 150-199 |
| 008 | 16 | PA | | | 3-0 | 25-31-21 | D00592 | | 9 | FM | GD02570 | | D.. | E | 275-299 |
| 009 | 20 | PA | | | 35-0 | 25-31-21 | D11840 | | 5 | | D12098 | | 5 | | 275-299 |
| 010 | 20 | PA | | | 35-0 | 25-31-21 | D11840 | | 6 | | D12098 | | 6 | | 275-299 |
| 011 | 20 | PA | | | 35-0 | 25-31-21 | D11840 | | 7 | | D12098 | | 7 | | 275-299 |
| 012 | 20 | PA | | | 1-0 | 25-31-21 | D00592 | | 10 | | SM00001 | | | S | 050-099 |
| 012 | 20 | PA | | | 156-0 | 25-31-21 | D00592 | | 10 | | SM00001 | | | S | 150-199 |
| 012 | 16 | PA | | | 2-0 | 25-31-21 | D00592 | | 10 | FM | SM00003 | | | S | 275-299 |
| 013 | 16 | PA | | | 133-0 | 25-31-21 | D04068P | | 10 | | SM00001 | | | S | 050-099 |
| 013 | 16 | PA | | | 2-0 | 25-31-21 | D04068P | | 10 | | SM00001 | | | S | 150-199, 275-299 |
| 014 | 12 | PA | | | 155-0 | 25-31-21 | SM00003 | | | S | SM00001 | | | S | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0210

Page 6

Jun 06/2008



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0216 | 286T0216 | | | P31 TO A2-L2-L DISC. AFT GALLEY CONTROL (continued) | | | | | | | | | | | | | |
| 015 | 20 | | PA | | 13-0 | 25-31-21 | D11840 | | 9 | | | | GD00026 | A.. | 2 | | 275-299 |
| 016 | 20 | | PA | | 13-0 | 25-31-21 | D11840 | | 10 | | | | GD00026 | A.. | 2 | | 275-299 |
| 031 | 18 | | PA | | 3-0 | SPARE | D00592 | | 14 | DK | | | GD02570 | D.. | E | | 280-299 |
| 035 | 20 | | PA | | 90-0 | 33-24-14 | D00592 | | 8 | | | | SP03490 | | S | | 275-276 |
| 035 | 20 | | PQ | BJ | 90-0 | 33-24-14 | D00592 | | 8 | | | | SP03490 | | S | | 277-299 |
| 035Z | | | | BJ | 0-0 | 33-24-14 | D00592 | | | DED | | | SP03490 | DED | | | 277-299 |
| 036 | 20 | | PA | | 90-0 | 33-24-14 | D00592 | | 12 | | | | SP03492 | | S | | 275-276 |
| 036 | 20 | | PQ | BK | 90-0 | 33-24-14 | D00592 | | 12 | | | | SP03492 | | S | | 277-299 |
| 036Z | | | | BK | 0-0 | 33-24-14 | D00592 | | | DED | | | SP03492 | DED | | | 277-299 |
| 037 | 20 | | PA | | 3-0 | 33-24-14 | D00592 | | 11 | | | | GD00173 | A.. | E | | 275-276 |
| 037 | 20 | | PQ | BL | 3-0 | 33-24-14 | D00592 | | 11 | | | | GD00173 | A.. | E | | 277-299 |
| 037Z | | | | BL | 0-0 | 33-24-14 | D00592 | | | DED | | | GD00173 | DED | | | 277-299 |
| 042 | 24 | | PK | | 1-0 | 25-31-21 | D00592 | | 4 | | | | SM00012 | | S | | 050-099 |
| 042 | 24 | | PK | | 156-0 | 25-31-21 | D00592 | | 4 | | | | SM00012 | | S | | 150-199 |
| 043 | 24 | | PK | | 1-0 | 25-31-21 | D00592 | | 5 | | | | SM00010 | | S | | 050-099 |
| 043 | 24 | | PK | | 156-0 | 25-31-21 | D00592 | | 5 | | | | SM00010 | | S | | 150-199 |
| 044 | 24 | | PK | | 1-0 | 25-31-21 | D00592 | | 6 | | | | SM00008 | | S | | 050-099 |
| 044 | 24 | | PK | | 156-0 | 25-31-21 | D00592 | | 6 | | | | SM00008 | | S | | 150-199 |
| 045 | 24 | | PK | | 1-0 | 25-31-21 | D00592 | | 7 | | | | SM00006 | | S | | 050-099 |
| 045 | 24 | | PK | | 156-0 | 25-31-21 | D00592 | | 7 | | | | SM00006 | | S | | 150-199 |
| 046 | 20 | | PA | | 23-0 | 25-31-31 | SM00006 | | | S | | | SP03666 | | S | | 050-099 |
| 046 | 20 | | PA | | 138-0 | 25-31-31 | SP03666 | | | S | | | SM00006 | | S | | 150-199 |
| 047 | 20 | | PA | | 23-0 | 25-31-31 | SM00008 | | | S | | | SP03664 | | S | | 050-099 |
| 047 | 20 | | PA | | 138-0 | 25-31-31 | SP03664 | | | S | | | SM00008 | | S | | 150-199 |
| 048 | 20 | | PA | | 23-0 | 25-31-31 | SM00010 | | | S | | | SP03662 | | S | | 050-099 |
| 048 | 20 | | PA | | 138-0 | 25-31-31 | SP03662 | | | S | | | SM00010 | | S | | 150-199 |
| 049 | 20 | | PA | | 23-0 | 25-31-31 | SM00012 | | | S | | | SP03660 | | S | | 050-099 |
| 049 | 20 | | PA | | 138-0 | 25-31-31 | SP03660 | | | S | | | SM00012 | | S | | 150-199 |
| 050 | 20 | | PA | | 23-0 | 25-31-31 | SM00001 | | | S | | | SP03658 | | S | | 050-099 |
| 050 | 20 | | PA | | 138-0 | 25-31-31 | SP03658 | | | S | | | SM00001 | | S | | 150-199 |
| 051 | 18 | | PA | | 116-0 | 30-71-25 | D04068P | | 4 | | | | SP03790 | | 9 | | 050-099 |
| 051 | 18 | | PA | | 140-0 | 30-71-25 | SP03790 | | | 9 | | | D04068P | | 4 | | 150-199 |
| 053 | 18 | | PA | | 23-0 | 30-71-25 | D00592 | | 11 | DK | | | SP03790 | | 9 | | 050-099 |
| 053 | 18 | | PA | | 24-0 | 30-71-25 | SP03790 | | | 9 | | | D00592 | | 11 | DK | 150-199 |
| 054 | 18 | | PA | | 3-0 | 30-71-25 | D00592 | | 12 | DK | | | GD00173 | A.. | E | | 050-099, 150-199 |
| 056 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 8 | | | | D12098 | | 8 | | 275-299 |
| 057 | 20 | | PA | | 13-0 | 25-31-21 | D11840 | | 11 | | | | GD00026 | A.. | 2 | | 275-299 |
| 058 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 13 | | | | D12098 | | 13 | | 275-299 |
| 059 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 14 | | | | D12098 | | 14 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0210

Page 7

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | | |
|--------------|-----------------|--|-------|-------------|------|----------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|---|--|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0216 | 286T0216 | P31 TO A2-L2-L DISC. AFT GALLEY CONTROL (continued) | | | | | | | | | | | | | | | | | | |
| 060 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 15 | | | | | | D12098 | | 15 | | | 275-299 |
| 061 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 16 | | | | | | D12098 | | 16 | | | 275-299 |
| 062 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 17 | | | | | | D12098 | | 17 | | | 275-299 |
| 063 | 20 | | PA | | 13-0 | 25-31-21 | D11840 | | 18 | | | | | | GD01126 | A.. | 2 | | | 275-299 |
| 064 | 20 | | PA | | 13-0 | 25-31-21 | D11840 | | 19 | | | | | | GD01126 | A.. | 2 | | | 275-299 |
| 065 | 20 | | PA | | 13-0 | 25-31-21 | D11840 | | 20 | | | | | | GD01126 | A.. | 2 | | | 275-299 |
| 066 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 22 | | | | | | D12098 | | 22 | | | 275-299 |
| 067 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 23 | | | | | | D12098 | | 23 | | | 275-299 |
| 068 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 24 | | | | | | D12098 | | 24 | | | 275-299 |
| 069 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 25 | | | | | | D12098 | | 25 | | | 275-299 |
| 070 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 26 | | | | | | D12098 | | 26 | | | 275-299 |
| 071 | 20 | | PA | | 13-0 | 25-31-21 | D11840 | | 27 | | | | | | GD01126 | A.. | 2 | | | 275-299 |
| 072 | 20 | | PA | | 13-0 | 25-31-21 | D11840 | | 28 | | | | | | GD01126 | A.. | 2 | | | 275-299 |
| 073 | 20 | | PA | | 13-0 | 25-31-21 | D11840 | | 29 | | | | | | GD01126 | A.. | 2 | | | 275-299 |
| 074 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 31 | | | | | | D12098 | | 31 | | | 275-299 |
| 075 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 32 | | | | | | D12098 | | 32 | | | 275-299 |
| 076 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 33 | | | | | | D12098 | | 33 | | | 275-299 |
| 077 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 34 | | | | | | D12098 | | 34 | | | 275-299 |
| 078 | 20 | | PA | | 35-0 | 25-31-21 | D11840 | | 35 | | | | | | D12098 | | 35 | | | 275-299 |
| 079 | 20 | | PA | | 13-0 | 25-31-21 | D11840 | | 36 | | | | | | GD01126 | A.. | 2 | | | 275-299 |
| 080 | 20 | | PA | | 13-0 | 25-31-21 | D11840 | | 37 | | | | | | GD01126 | A.. | 2 | | | 275-299 |
| 081 | 20 | | PA | | 13-0 | 25-31-21 | D11840 | | 38 | | | | | | GD01126 | A.. | 2 | | | 275-299 |
| 087 | 18 | | PA | | 27-0 | SPARE | D00592 | | 13 | DK | | | | | SP05308 | | | S | | 280-299 |
| 102 | 20 | | PA | | 16-0 | 33-24-12 | D00592 | | 2 | | | | | | GD00932 | A.. | 2 | | | 050-099 |
| 102 | 20 | | PA | | 17-0 | 33-24-12 | GD00932 | | A.. | 2 | | | | | D00592 | | 2 | | | 150-199 |
| 103 | 20 | | PA | | 23-0 | 33-24-12 | D00592 | | 3 | | | | | | SP03898 | | | 9 | | 050-099 |
| 103 | 20 | | PA | | 23-0 | 33-24-12 | SP03898 | | | 9 | | | | | D00592 | | 3 | | | 150-199 |
| 104 | 20 | | PA | | 23-0 | 33-24-12 | D00592 | | 1 | | | | | | SP03900 | | | 9 | | 050-099 |
| 104 | 20 | | PA | | 23-0 | 33-24-12 | SP03900 | | | 9 | | | | | D00592 | | 1 | | | 150-199 |
| W0218 | 286T0218 | P6 TO E3-S1-MAIN BAT CHGR OUTPUT | | | | | | | | | | | | | | | | | | |
| 002 | 04 | | PA | | 3-0 | 24-31-11 | M00218 | | - | G | | | | | GD01878 | D.. | F | | | ALL |
| 003 | 06 | | PA | | 20-0 | 24-33-11 | M00217 | | + | G | | | | | K00104 | A2 | E | | | ALL |
| 004 | 06 | | PA | | 4-0 | 24-33-11 | M00217 | | - | F | | | | | GD01884 | D.. | E | | | ALL |
| 005 | 04 | | PA | | 21-0 | 24-31-11 | TB5014 | | 2 | G | | | | | M00218 | | + | H | | ALL |
| W0219 | 286T0219 | POWER DISTRIBUTION LEFT, P11 TO E2 & E5 | | | | | | | | | | | | | | | | | | |
| 001 | 22 | | PA | | 37-0 | 27-09-11 | D04273P | | 1 | | | | | | D04945P | | 1 | | | ALL |
| 002 | 22 | | PA | | 37-0 | 27-09-11 | D04273P | | 2 | | | | | | D04945P | | 2 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0210
Page 8
Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0219 | 286T0219 | | | POWER DISTRIBUTION LEFT, P11 TO E2 & E5 (continued) | | | | | | | | | | | | | |
| 003 | 20 | | PA | 37-0 | SPARE | D04273P | | 3 | | | | | D04945P | 3 | | | 050-099, 150-199, 275-278 |
| 004 | 20 | | PA | 37-0 | SPARE | D04273P | | 4 | | | | | D04945P | 4 | | | ALL |
| 005 | 22 | | PA | 38-0 | 34-61-11 | D04273P | | 5 | | | | | D04217J | 5 | | | ALL |
| 006 | 24 | | PK | 38-0 | 34-61-11 | D04273P | | 6 | | | | | D04217J | 6 | | | ALL |
| 007 | 22 | | PA | 38-0 | SPARE | D04273P | | 7 | | | | | D04217J | 7 | | | 050-099, 150-199 |
| 008 | 24 | | PK | 38-0 | SPARE | D04273P | | 8 | | | | | D04217J | 8 | | | ALL |
| 009 | 20 | | PA | 38-0 | 34-53-11 | D04273P | | 9 | | | | | D04217J | 9 | | | 050-099, 155-199, 275-299 |
| 009 | 22 | | PA | 38-0 | 34-53-11 | D04273P | | 9 | | | | | D04217J | 9 | | | 150-154 |
| 010 | 22 | | PA | 38-0 | 34-55-11 | D04273P | | 10 | | | | | D04217J | 10 | | | ALL |
| 011 | 20 | | PA | 38-0 | SPARE | D04273P | | 11 | | | | | D04217J | 11 | | | ALL |
| 013 | 22 | | PA | 39-0 | 31-31-11 | D04273P | | 13 | | | | | D04215J | 3 | | | ALL |
| 014 | 22 | | PA | 39-0 | 31-31-11 | D04273P | | 14 | | | | | D04215J | 4 | | | ALL |
| 015 | 20 | | PA | 39-0 | SPARE | D04273P | | 15 | | | | | D04215J | 5 | | | ALL |
| 016 | 20 | | PA | 39-0 | SPARE | D04273P | | 16 | | | | | D04215J | 2 | | | ALL |
| 017 | 22 | | PA | 41-0 | 23-21-11 | D04273P | | 17 | | | | | D04213J | 2 | | | ALL |
| 019 | 22 | | PA | 41-0 | 23-22-11 | D04273P | | 19 | | | | | D04213J | 3 | | | ALL |
| 020 | 22 | | PA | 41-0 | 23-34-11 | D04273P | | 20 | | | | | D04213J | 5 | | | ALL |
| 021 | 16 | | PA | 41-0 | 23-12-31 | D04273P | | 21 | | | | | D04213J | 7 | | | ALL |
| 022 | 22 | | PA | 41-0 | SPARE | D04273P | | 22 | | | | | D04213J | 6 | | | 050-099, 151-152, 275-299 |
| 022 | 22 | | PA | 41-0 | SPARE | D04273P | | | CAP | Y | | | D04213J | 6 | | | 150, 153-199 |
| 024 | 20 | | PA | 41-0 | SPARE | D04211J | | 1 | | | | | D04273P | 24 | | | 050-099 |
| 024 | 20 | | PA | 41-0 | SPARE | D04273P | | | CAP | Y | | | D04211J | 1 | | | 150, 153-199 |
| 024 | 20 | | PA | 41-0 | SPARE | D04273P | | 24 | | | | | D04211J | 1 | | | 151-152, 275-276, 280-299 |
| 025 | 20 | | PA | 41-0 | 23-11-11 | D04211J | | 2 | | | | | D04273P | 25 | | | 050-099 |
| 025 | 20 | | PA | 41-0 | 23-11-11 | D04273P | | 25 | | | | | D04211J | 2 | | | 150-199, 275-299 |
| 026 | 20 | | PA | 41-0 | 23-11-11 | D04211J | | 3 | | | | | D04273P | 26 | | | 050-099 |
| 026 | 20 | | PA | 41-0 | 23-11-11 | D04273P | | 26 | | | | | D04211J | 3 | | | 150-199, 275-299 |
| 027 | 20 | | PA | 41-0 | 23-11-11 | D04211J | | 7 | | | | | D04273P | 27 | | | 050-099 |
| 027 | 20 | | PA | 41-0 | 23-11-11 | D04273P | | 27 | | | | | D04211J | 7 | | | 150-199, 275-299 |
| 028 | 20 | | PA | 69-0 | SPARE | D04273P | | 28 | | | | | D04223J | 2 | | | 050-099 |
| 028 | 20 | | PA | 69-1 | SPARE | D04273P | | 28 | | | | | D04223J | 2 | | | 150-199, 275-299 |
| 029 | 22 | | PA | 69-0 | 34-33-11 | D04273P | | 29 | | | | | D04223J | 1 | | | 050-099 |
| 029 | 22 | | PA | 69-1 | 34-33-11 | D04273P | | 29 | | | | | D04223J | 1 | | | 150-199, 275-299 |
| 030 | 20 | | PA | 69-0 | SPARE | D04273P | | 30 | | | | | D04223J | 3 | | | 050-099 |
| 030 | 20 | | PA | 69-1 | SPARE | D04273P | | 30 | | | | | D04223J | 3 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0210

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0219 | 286T0219 | | | POWER DISTRIBUTION LEFT, P11 TO E2 & E5 (continued) | | | | | | | | | | | |
| 031 | 22 | | PA | 19-0 | 34-57-11 | D04273P | | 31 | | | SP00207 | | 9 | | ALL |
| 032 | 20 | | PA | 3-0 | 23-11-11 | D04211J | | 8 | | | GD00527 | A.. | E | | 050-099 |
| 032 | 20 | | PA | 3-0 | 23-11-11 | GD00527 | | | A.. | E | D04211J | | 8 | | 150-199, 275-299 |
| 033 | 20 | | PA | 3-0 | 23-22-11 | GD00527 | | | A.. | E | D04213J | | 8 | | ALL |
| 034 | 20 | | PA | 70-0 | SPARE | D04219J | | 4 | | | D04273P | | 34 | | 050-099 |
| 034 | 20 | | PA | 69-0 | SPARE | D04273P | | 34 | | | D04219J | | 4 | | 150-199, 275-299 |
| 035 | 20 | | PA | 70-0 | SPARE | D04219J | | 5 | | | D04273P | | 35 | | 050-099 |
| 035 | 20 | | PA | 69-0 | SPARE | D04273P | | 35 | | | D04219J | | 5 | | 150-199, 275-299 |
| 036 | 22 | | PA | 39-0 | SPARE | D04273P | | 33 | | | D04215J | | 8 | | 150-199 |
| 037 | 22 | | PA | 39-0 | 31-35-11 | D04273P | | 37 | | | D04215J | | 10 | | ALL |
| 039 | 22 | | PA | 39-0 | 31-31-15 | D04273P | | 32 | | | D04215J | | 7 | | ALL |
| 045 | 24 | | PK | 38-0 | 34-53-13 | D04273P | | 39 | | | D04217J | | 15 | | 050-099, 150-154, 156-157, 166-199, 277-299 |
| 045 | 24 | | PK | 38-0 | 34-53-13 | D04273P | | 23 | | | D04217J | | 15 | | 155, 162-165, 275-276 |
| 046 | 22 | | PA | 39-0 | 31-36-11 | D04273P | | 18 | | | D04215J | | 6 | | ALL |
| 049 | 16 | | PA | 38-0 | 23-25-11 | D04273P | | 23 | | | D04217J | | 12 | FM | 156-157, 166-199, 277-299 |
| 050 | 24 | | PK | 41-0 | 23-25-14 | D04273P | | 24 | | | D04211J | | 6 | | 150, 153-199, 277-278 |

WIRE LIST
D280T132

91-21-11
Section W0210
Page 10 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|----|-----------------|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0220 | | 286T0220 | | | P32 TO F1-R1-FWD GALLEY POWER FEEDER | | | | | | | | | | | |
| 001 | 04 | | QY | | 38-0 | 25-31-11 | SM00001 | | GF | | M01617 | A2 | H4 | | 050-099, 150-199 | |
| 002 | 04 | | QY | | 38-0 | 25-31-11 | SM00002 | | GF | | M01617 | B2 | H4 | | 050-099, 150-199 | |
| 003 | 04 | | QY | | 37-0 | 25-31-11 | SM00003 | | GF | | M01617 | C2 | H4 | | 050-099, 150-199 | |
| 004 | 06 | | HA | | 3-0 | 25-31-11 | D00904 | | D | | GD05680 | A.. | G | | 050-099 | |
| 004 | 06 | | HA | | 4-0 | 25-31-11 | D00904 | | D | | GD05680 | A.. | G | | 150-199 | |
| 004 | 04 | | HA | | 1-7 | 25-31-11 | D00904 | | D | | GD01820 | A.. | G | | 275-299 | |
| 005 | 06 | | HA | | 3-0 | 25-31-11 | D00904 | | A | | SM00001 | | GF | | 050-099 | |
| 005 | 06 | | HA | | 5-0 | 25-31-11 | D00904 | | A | | SM00001 | | GF | | 150-199 | |
| 005 | 04 | | HA | | 29-4 | 25-31-11 | D00904 | | A | | M00225 | A2 | H | | 275-299 | |
| 006 | 06 | | HA | | 3-5 | 25-31-11 | D00904 | | B | | SM00002 | | GF | | 050-099 | |
| 006 | 06 | | HA | | 5-0 | 25-31-11 | D00904 | | B | | SM00002 | | GF | | 150-199 | |
| 006 | 04 | | HA | | 28-11 | 25-31-11 | D00904 | | B | | M00225 | B2 | H | | 275-299 | |
| 007 | 06 | | HA | | 3-5 | 25-31-11 | D00904 | | C | | SM00003 | | GF | | 050-099 | |
| 007 | 06 | | HA | | 5-0 | 25-31-11 | D00904 | | C | | SM00003 | | GF | | 150-199 | |
| 007 | 04 | | HA | | 28-6 | 25-31-11 | D00904 | | C | | M00225 | C2 | H | | 275-299 | |
| W0222 | | 286T0222 | | | P4 TO R W/B DISCONNECT-R2-R IDG CONTROL | | | | | | | | | | | |
| 001 | 18 | | PQ | L | 46-3 | 24-11-21 | D04036J | | 4 | | D04400J | | 4 | | 050-099 | |
| 001 | 18 | | PQ | L | 56-4 | 24-11-21 | D04036J | | 4 | | D04400J | | 4 | | 150-154, 162-163, 275-276 | |
| 001 | 18 | | PQ | L | 63-4 | 24-11-21 | D04036J | | 4 | | D04400J | | 4 | | 155-157, 164-199, 277-299 | |
| 001Z | | | | L | 0-0 | 24-11-21 | D04036J | | DED | | D04400J | | DED | | ALL | |
| 003 | 24 | | PK | | 46-0 | 24-11-21 | D04630J | | 16 | | D04034J | | 16 | | 050-099 | |
| 003 | 24 | | PK | | 56-1 | 24-11-21 | D04630J | | 16 | | D04034J | | 16 | | 150-154, 162-163, 275-276 | |
| 003 | 24 | | PK | | 63-4 | 24-11-21 | D04630J | | 16 | | D04034J | | 16 | | 155-157, 164-199, 277-299 | |
| 007 | 24 | | PK | | 25-2 | 24-51-51 | D04794P | | 34 | | D04078J | | 17 | | ALL | |
| 009 | 22 | | PA | | 14-10 | 25-31-11 | D04012P | | 5 | | D04034J | | 25 | | ALL | |
| 011 | 24 | | PK | | 14-9 | 29-11-12 | D04012P | | 7 | | D04078J | | 22 | | ALL | |
| 013 | 24 | | PK | | 46-11 | 25-31-11 | D04012P | | 9 | | D00906 | | 4 | | 050-099, 150-199 | |
| 013 | 24 | | PK | | 24-8 | 25-31-11 | D04012P | | 9 | | D00906 | | 4 | | 275-299 | |
| 014 | 24 | | PK | | 46-11 | 25-31-11 | D04012P | | 10 | | D00906 | | 5 | | 050-099, 150-199 | |
| 014 | 24 | | PK | | 24-8 | 25-31-11 | D04012P | | 10 | | D00906 | | 5 | | 275-299 | |
| 015 | 24 | | PK | | 46-11 | 25-31-11 | D04012P | | 11 | | D00906 | | 6 | | 050-099, 150-199 | |
| 015 | 24 | | PK | | 24-8 | 25-31-11 | D04012P | | 11 | | D00906 | | 6 | | 275-299 | |
| 016 | 24 | | PK | | 46-11 | 25-31-11 | D04012P | | 12 | | D00906 | | 7 | | 050-099, 150-199 | |
| 016 | 24 | | PK | | 24-8 | 25-31-11 | D04012P | | 12 | | D00906 | | 7 | | 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0220

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0222 | 286T0222 | | | P4 TO R W/B DISCONNECT-R2-R IDG CONTROL (continued) | | | | | | | | | | | |
| 019 | 20 | | PA | | 15-2 | 25-31-11 | D04036J | | 18 | | D04062P | | 2 | | 275-276 |
| 019 | 20 | | PA | | 15-2 | SPARE | D04036J | | 18 | | D04062P | | 2 | | 277-299 |
| 026 | 20 | | PA | | 21-6 | 25-31-11 | SM00004 | | | W | D00906 | | 10 | | 050-099 |
| 026 | 20 | | PA | | 24-3 | 25-31-11 | D00906 | | 10 | FM | SM00004 | | 9 | | 150-199 |
| 027 | 22 | | PA | | 25-4 | 25-31-11 | D04794P | | 5 | | D04034J | | 4 | | ALL |
| 028 | 24 | | PK | | 14-10 | 24-51-71 | D04012P | | 4 | | D04034J | | 18 | | ALL |
| 030 | 24 | | PK | | 29-6 | 24-11-21 | D06234P | | A03 | \$D | D04034J | | 20 | | 050-099 |
| 030 | 24 | | PK | | 29-6 | 24-11-21 | D06234P | | A03 | | D04034J | | 20 | | 150-199, 275-299 |
| 031 | 24 | | PK | | 25-4 | 24-11-21 | D04794P | | 9 | | D04034J | | 17 | | ALL |
| 033 | 20 | | PA | | 3-0 | 25-31-11 | D00906 | | 9 | | GD04192 | | D.. | 2 | 050-099, 150-199 |
| 033 | 20 | | PA | | 1-10 | 25-31-11 | D00906 | | 9 | | GD03046 | | D.. | G | 275-278 |
| 033 | 16 | | PA | | 1-10 | 25-31-11 | D00906 | | 9 | FM | GD03046 | | D.. | G | 280-299 |
| 038 | 24 | | PK | | 25-4 | 24-22-21 | D04794P | | 43 | | D04034J | | 24 | | ALL |
| 039 | 20 | | PA | | 25-4 | 24-22-21 | D04034J | | 29 | | D04794P | | 12 | | ALL |
| 040 | 20 | | PA | | 25-4 | 24-22-21 | D04034J | | 30 | | D04794P | | 13 | | ALL |
| 041 | 24 | | PK | | 25-4 | 24-22-21 | D04034J | | 31 | | D04794P | | 14 | | ALL |
| 042 | 24 | | PK | | 25-4 | 24-22-21 | D04034J | | 32 | | D04794P | | 15 | | ALL |
| 043 | 20 | | PA | | 14-10 | 24-22-21 | D04034J | | 33 | | D04012P | | 14 | | ALL |
| 044 | 20 | | PA | | 14-10 | 24-22-21 | D04034J | | 34 | | D04012P | | 15 | | ALL |
| 045 | 20 | | PA | | 14-10 | 24-22-21 | D04034J | | 35 | | D04012P | | 16 | | ALL |
| 046 | 24 | | PK | | 14-10 | 24-22-22 | D04034J | | 36 | | D04012P | | 17 | | ALL |
| 047 | 24 | | PK | | 14-10 | 24-22-21 | D04034J | | 37 | | D04012P | | 18 | | ALL |
| 048 | 18 | | PA | | 15-2 | 24-22-21 | D04036J | | 7 | | D04062P | | 10 | | ALL |
| 049 | 24 | | PK | | 25-4 | 24-11-21 | D04034J | | 38 | | D04794P | | 16 | | ALL |
| 050 | 24 | | PK | | 25-4 | 24-22-22 | D04034J | | 39 | | D04794P | | 17 | | ALL |
| 051 | 20 | | PA | | 25-4 | 24-22-22 | D04034J | | 40 | | D04794P | | 18 | | ALL |
| 052 | 20 | | PA | | 14-10 | 24-22-22 | D04034J | | 41 | | D04012P | | 19 | | ALL |
| 053 | 20 | | PA | | 14-10 | 24-22-22 | D04034J | | 42 | | D04012P | | 20 | | ALL |
| 054 | 20 | | PA | | 14-10 | 24-22-22 | D04034J | | 43 | | D04012P | | 21 | | ALL |
| 055 | 24 | | PK | | 14-10 | 24-22-22 | D04034J | | 44 | | D04012P | | 22 | | ALL |
| 056 | 24 | | PK | | 14-10 | 24-22-22 | D04034J | | 45 | | D04012P | | 23 | | ALL |
| 057 | 18 | | PA | | 15-2 | 24-22-22 | D04036J | | 8 | | D04062P | | 11 | | ALL |
| 058 | 24 | | PK | | 29-4 | 24-27-21 | D04078J | | 13 | | D06234P | | A10 | \$D | ALL |
| 060 | 22 | | PA | | 25-2 | 24-51-51 | D04078J | | 15 | | D04794P | | 26 | | ALL |
| 061 | 22 | | PA | | 25-2 | 24-51-51 | D04078J | | 16 | | D04794P | | 25 | | ALL |
| 062 | 24 | | PK | | 15-1 | 24-51-51 | D04036J | | 12 | | D04012P | | 32 | | ALL |
| 063 | 24 | | PK | | 15-1 | 24-51-23 | D04036J | | 13 | | D04012P | | 33 | | ALL |
| 065 | 24 | | PK | | 31-5 | 24-27-21 | D04012P | | 34 | | D06234P | | A08 | \$D | ALL |
| 066 | 24 | | PK | | 31-5 | 24-27-21 | D04012P | | 35 | | D06234P | | A09 | \$D | ALL |

WIRE LIST

D280T132

91-21-11

Section W0220

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0222 | 286T0222 | | | P4 TO R W/B DISCONNECT-R2-R IDG CONTROL (continued) | | | | | | | | | | | |
| 068 | 24 | | PK | 31-5 | 24-28-11 | D04012P | | 37 | | | D06234P | A04 | \$D | | ALL |
| 069 | 24 | | PK | 23-1 | 24-51-23 | D04012P | | 38 | | | D04794P | | | | ALL |
| 070 | 24 | | PK | 23-1 | 24-51-23 | D04012P | | 39 | | | D04794P | | | | ALL |
| 072 | 22 | | PA | 22-9 | 33-27-11 | D00906 | | 8 | | | SP00720 | | 9 | | 275-299 |
| 073 | 22 | | PA | 22-9 | 33-27-11 | D00906 | | 11 | | | SP00724 | | 9 | | 275-299 |
| 074 | 20 | | PA | 1-10 | 33-27-11 | D00906 | | 12 | | | GD01820 | A.. | G | | 275-299 |
| 076 | 22 | | PQ | 25-2 | 29-11-31 | D04078J | | 19 | | | D04794P | | 35 | | ALL |
| 076Z | | | | 0-0 | 29-11-31 | D04078J | | DED | | | D04794P | DED | | | ALL |
| 077 | 22 | | PA | 23-1 | 29-32-11 | D04012P | | 41 | | | D04794P | | 36 | | ALL |
| 080 | 24 | | PK | 14-10 | 24-51-31 | D04012P | | 42 | | | D04034J | | 46 | | ALL |
| 081 | 20 | | PA | 14-10 | 24-22-22 | D04012P | | 43 | | | D04034J | | 47 | | ALL |
| 082 | 24 | | PK | 14-10 | 24-51-31 | D04012P | | 44 | | | D04034J | | 48 | | ALL |
| 083 | 20 | | PA | 14-10 | 24-22-22 | D04012P | | 45 | | | D04034J | | 49 | | ALL |
| 084 | 24 | | PV | 14-10 | 29-11-31 | D04012P | | 46 | | | D04034J | | 50 | | ALL |
| 084Z | | | | 0-0 | 29-11-31 | D04012P | | DED | | | D04034J | DED | | | ALL |
| 085 | 24 | | PV | 14-10 | 29-11-31 | D04012P | | 47 | | | D04034J | | 51 | | ALL |
| 085Z | | | | 0-0 | 29-11-31 | D04012P | | DED | | | D04034J | DED | | | ALL |
| 086 | 24 | | PV | 14-10 | 29-11-31 | D04012P | | 48 | | | D04034J | | 52 | | ALL |
| 086Z | | | | 0-0 | 29-11-31 | D04012P | | DED | | | D04034J | DED | | | ALL |
| 087 | 24 | | PK | 23-2 | 24-51-31 | D04062P | | 7 | | | D04794P | | 1 | | ALL |
| 088 | 24 | | PK | 23-2 | 24-51-31 | D04062P | | 5 | | | D04794P | | 4 | | ALL |
| 089 | 24 | | PK | 25-4 | 24-51-31 | D04794P | | 24 | | | D04034J | | 28 | | ALL |
| 090 | 24 | | PK | 14-10 | 24-51-52 | D04012P | | 49 | | | D04034J | | 53 | | ALL |
| 091 | 24 | | PK | 23-1 | 24-22-22 | D04012P | | 8 | | | D04794P | | 42 | | ALL |
| 093 | 10 | | PA | 24-9 | 25-31-11 | D10930 | | A | | | D10932 | | A | | 050-099 |
| 093 | 10 | | PA | 24-9 | 25-31-11 | D10932 | | A | | | D10930 | | A | | 150-199 |
| 093 | 20 | | PA | 19-1 | 25-31-11 | D10932 | | 1 | | | D10930 | | 1 | | 277-278 |
| 093 | 20 | | PA | 23-4 | 25-31-11 | D10932 | | 1 | | | D10930 | | 1 | | 280-299 |
| 094 | 10 | | PA | 24-9 | 25-31-11 | D10930 | | B | | | D10932 | | B | | 050-099 |
| 094 | 10 | | PA | 24-9 | 25-31-11 | D10932 | | B | | | D10930 | | B | | 150-199 |
| 094 | 20 | | PA | 19-1 | 25-31-11 | D10932 | | 2 | | | D10930 | | 2 | | 277-278 |
| 094 | 20 | | PA | 23-4 | 25-31-11 | D10932 | | 2 | | | D10930 | | 2 | | 280-299 |
| 095 | 10 | | PA | 24-9 | 25-31-11 | D10930 | | C | | | D10932 | | C | | 050-099 |
| 095 | 10 | | PA | 24-9 | 25-31-11 | D10932 | | C | | | D10930 | | C | | 150-199 |
| 095 | 20 | | PA | 19-1 | 25-31-11 | D10932 | | 3 | | | D10930 | | 3 | | 277-278 |
| 095 | 20 | | PA | 23-4 | 25-31-11 | D10932 | | 3 | | | D10930 | | 3 | | 280-299 |
| 096 | 10 | | PA | 2-2 | 25-31-11 | D10930 | | D | | | GD01820 | A.. | G | | 050-099, 150-199 |
| 096 | 20 | | PA | 14-5 | 25-31-11 | D10932 | | 4 | | | GD04192 | A.. | 2 | | 277-278 |
| 096 | 20 | | PA | 15-4 | 25-31-11 | D10932 | | 4 | | | GD04192 | A.. | 2 | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0220

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0222 | 286T0222 | | | P4 TO R W/B DISCONNECT-R2-R IDG CONTROL (continued) | | | | | | | | | | | |
| 100 | 20 | | PA | | 45-10 | SPARE | D04630J | 24 | | | D04078J | 24 | | | 050-099 |
| 100 | 20 | | PA | | 55-11 | SPARE | D04630J | 24 | | | D04078J | 24 | | | 150-154, 162-163, 275-276 |
| 100 | 20 | | PA | | 63-2 | SPARE | D04630J | 24 | | | D04078J | 24 | | | 155-157, 164-199, 277-299 |
| 108 | 24 | | PK | | 14-9 | 29-11-12 | D04012P | 3 | | | D04078J | 20 | | | ALL |
| 109 | 24 | | PV | P | 14-9 | 29-11-31 | D04062P | 16 | | | D04078J | 18 | | | ALL |
| 109Z | | | | P | 0-0 | 29-11-31 | D04062P | DED | | | D04078J | DED | | | ALL |
| 112 | 24 | | PK | | 29-6 | 24-11-21 | D04034J | 55 | | | D06234P | A02 | \$D | | ALL |
| 113 | 24 | | PK | | 25-4 | 24-22-21 | D04794P | 11 | | | D04034J | 19 | | | ALL |
| 114 | 24 | | PK | | 23-1 | 24-51-71 | D04012P | 50 | | | D04794P | 6 | | | ALL |
| 115 | 24 | | PK | | 22-0 | 24-11-21 | D06234P | A05 | \$D | | D04078J | 21 | | | ALL |
| 116 | 24 | | PK | | 0-7 | SPARE | D06234P | A06 | \$D | | D06234P | CAP | Y | | ALL |
| 117 | 24 | | PK | | 0-7 | SPARE | D06234P | A07 | \$D | | D06234P | CAP | Y | | ALL |
| 119 | 24 | | PK | | 0-7 | SPARE | D06234P | A12 | \$D | | D06234P | CAP | Y | | ALL |
| 120 | 24 | | PK | | 0-7 | SPARE | D06234P | A13 | \$D | | D06234P | CAP | Y | | ALL |
| 121 | 24 | | PK | | 0-7 | SPARE | D06234P | A14 | \$D | | D06234P | CAP | Y | | ALL |
| 122 | 24 | | PK | | 0-7 | SPARE | D06234P | A15 | \$D | | D06234P | CAP | Y | | ALL |
| 123 | 24 | | PK | | 0-7 | SPARE | D06234P | A16 | \$D | | D06234P | CAP | Y | | ALL |
| 124 | 24 | | PK | | 0-7 | SPARE | D06234P | A17 | \$D | | D06234P | CAP | Y | | ALL |
| 125 | 24 | | PK | | 0-7 | SPARE | D06234P | A18 | \$D | | D06234P | CAP | Y | | 150-199 |
| 126 | 24 | | PK | | 0-7 | SPARE | D06234P | A19 | \$D | | D06234P | CAP | Y | | 150-199 |
| 127 | 24 | | PK | | 23-1 | 24-27-21 | D04794P | 28 | | | D04012P | 51 | | | ALL |
| 128 | 24 | | PK | | 23-1 | 24-27-21 | D04794P | 29 | | | D04012P | 52 | | | ALL |
| 129 | 24 | | PK | | 25-2 | 24-27-21 | D04794P | 30 | | | D04078J | 14 | | | ALL |
| 130 | 16 | | PA | | 23-2 | SPARE | D04794P | 7 | FL | | D04062P | 8 | | | 280-299 |
| 131 | 18 | | PA | | 21-11 | 25-31-11 | D04794P | 8 | DL | | SM00004 | | W | | 050-099 |
| 131 | 18 | | PA | | 19-2 | 25-31-11 | D04794P | 8 | FL | | SM00004 | | | 9 | 150-199 |
| 131 | 16 | | PA | | 20-1 | 25-31-11 | D04794P | 8 | FN | | D00906 | 10 | FO | | 275-299 |
| 132 | 24 | | PK | | 14-9 | 29-11-12 | D04012P | 36 | | | D04078J | 23 | | | ALL |
| 135 | 24 | | PK | | 29-6 | 24-11-21 | D06234P | A11 | \$D | | D04034J | 23 | | | ALL |
| 136 | 20 | | PA | | 3-7 | 25-31-11 | D10926 | 10 | | | SM00004 | | W | | 050-099 |
| 136 | 20 | | PA | | 1-6 | 25-31-11 | D10926 | 10 | | | SM00004 | | 9 | | 150-199 |
| 136 | 20 | | PA | | 25-1 | 25-31-11 | D10926 | 1 | | | D10924 | 1 | | | 275-299 |
| 138 | 20 | | PA | | 25-1 | 25-31-11 | D10926 | 3 | | | D10924 | 3 | | | 280-299 |
| 139 | 20 | | PA | | 1-10 | 25-31-11 | D10926 | 9 | | | GD03046 | D.. | G | | 050-099, 150-199 |
| 139 | 20 | | PA | | 24-8 | 25-31-11 | D10926 | 3 | | | GD01820 | A.. | G | | 275-278 |
| 164 | 16 | | PA | | 23-2 | 25-31-12 | D04062P | 15 | | | D04794P | 45 | FL | | 050-099, 150-199 |
| 165 | 20 | | PA | | 5-0 | 33-22-31 | D00906 | 1 | | | SP00246 | | S | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0220

Page 4

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0222 | 286T0222 | | | P4 TO R W/B DISCONNECT-R2-R IDG CONTROL (continued) | | | | | | | | | | | |
| 165 | 20 | | PA | | 5-0 | 33-22-31 | SP00246 | | S | | D00906 | 1 | | | 150-199 |
| 166 | 20 | | PA | | 3-0 | 33-22-31 | D00906 | 2 | | | GD01114 | A.. | E | | 050-099 |
| 166 | 20 | | PA | | 3-0 | 33-22-31 | GD01114 | A.. | E | | D00906 | 2 | | | 150-199 |
| 167 | 18 | | PA | | 22-10 | 33-51-12 | SP03580 | | S | | D10926 | 5 | DK | | 150-157 |
| 168 | 18 | | PA | | 1-10 | 33-51-12 | GD03046 | D.. | G | | D10926 | 6 | DK | | 150-157 |
| 169 | 20 | | PA | | 5-0 | 35-21-13 | D00906 | 13 | | | SP03640 | | S | | 050-099 |
| 169 | 20 | | PA | | 5-0 | 35-21-13 | SP03640 | | S | | D00906 | 13 | | | 150-199 |
| 170 | 20 | | PA | | 24-3 | 35-21-13 | D00906 | 14 | | | GD03046 | D.. | G | | 050-099 |
| 170 | 20 | | PA | | 24-3 | 35-21-13 | GD03046 | D.. | G | | D00906 | 14 | | | 150-199 |
| 171 | 24 | | PK | | 15-1 | 31-31-26 | D04036J | 14 | | | D04012P | 53 | | | 050-099 |
| 171 | 24 | | PK | | 15-1 | 31-31-26 | D04012P | 53 | | | D04036J | 14 | | | 150-199, 275-299 |
| 172 | 24 | | PV | AB | 15-1 | 31-31-26 | D04036J | 15 | | | D04012P | 54 | | | 050-099 |
| 172 | 24 | | PV | AB | 15-1 | 31-31-26 | D04012P | 54 | | | D04036J | 15 | | | 150-199, 275-299 |
| 172Z | | | | AB | 0-0 | 31-31-26 | D04036J | DED | | | D04012P | DED | | | 050-099 |
| 172Z | | | | AB | 0-0 | 31-31-26 | D04012P | DED | | | D04036J | DED | | | 150-199, 275-299 |
| 177 | 18 | | PA | | 24-9 | 30-71-25 | D04062P | 8 | | | D10926 | 11 | DK | | 050-099, 150-199 |
| 178 | 18 | | PA | | 47-0 | 30-71-25 | D04062P | 9 | | | D00906 | 11 | DK | | 050-099, 150-199 |
| 179 | 18 | | PA | | 3-0 | 30-71-25 | D00906 | 12 | DK | | GD04192 | A.. | 2 | | 050-099, 150-199 |
| 180 | 18 | | PA | | 6-2 | 30-71-25 | D10926 | 12 | DK | | GD01236 | A.. | 2 | | 050-099, 150-199 |
| 183 | 20 | | PA | | 23-1 | 24-51-72 | D04012P | 40 | | | D04794P | 10 | | | 050-099, 162-164, 276 |
| 183 | 20 | | PA | | 23-1 | SPARE | D04012P | 40 | | | D04794P | 10 | | | 155-157, 165-199, 277-299 |
| 201B | 24 | | PW | A | 46-0 | 24-11-21 | D04630J | 1 | | | D04034J | 1 | | | 050-099 |
| 201B | 24 | | PW | A | 56-1 | 24-11-21 | D04630J | 1 | | | D04034J | 1 | | | 150-154, 162-163, 275-276 |
| 201B | 24 | | PW | A | 63-4 | 24-11-21 | D04630J | 1 | | | D04034J | 1 | | | 155-157, 164-199, 277-299 |
| 201R | 24 | | PW | A | 0-0 | 24-11-21 | D04630J | 2 | | | D04034J | 2 | | | ALL |
| 201Z | | | | A | 0-0 | 24-11-21 | D04630J | 3 | | | D04034J | 3 | | | ALL |
| 202B | 20 | | PR | B | 46-0 | 24-21-21 | D04630J | 5 | | | D04034J | 5 | | | 050-099 |
| 202B | 20 | | PR | B | 56-1 | 24-21-21 | D04630J | 5 | | | D04034J | 5 | | | 150-154, 162-163, 275-276 |
| 202B | 20 | | PR | B | 63-4 | 24-21-21 | D04630J | 5 | | | D04034J | 5 | | | 155-157, 164-199, 277-299 |
| 202R | 20 | | PR | B | 0-0 | 24-21-21 | D04630J | 6 | | | D04034J | 6 | | | ALL |
| 202Z | | | | B | 0-0 | 24-21-21 | D04630J | 7 | | | D04034J | 7 | | | ALL |
| 203B | 24 | | PL | D | 46-0 | 24-11-21 | D04630J | 12 | | | D04034J | 12 | | | 050-099 |
| 203B | 24 | | PL | D | 56-1 | 24-11-21 | D04630J | 12 | | | D04034J | 12 | | | 150-154, 162-163, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0220

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0222 | 286T0222 | | | P4 TO R W/B DISCONNECT-R2-R IDG CONTROL (continued) | | | | | | | | | | | |
| 203B | 24 | PL | D | 63-4 | 24-11-21 | D04630J | 12 | | | D04034J | 12 | | | 155-157, 164-199, 277-299 | |
| 203R | 24 | PL | D | 0-0 | 24-11-21 | D04630J | 13 | | | D04034J | 13 | | | ALL | |
| 204B | 24 | PL | E | 46-0 | 24-11-21 | D04630J | 14 | | | D04034J | 14 | | | 050-099 | |
| 204B | 24 | PL | E | 56-1 | 24-11-21 | D04630J | 14 | | | D04034J | 14 | | | 150-154, 162-163, 275-276 | |
| 204B | 24 | PL | E | 63-4 | 24-11-21 | D04630J | 14 | | | D04034J | 14 | | | 155-157, 164-199, 277-299 | |
| 204R | 24 | PL | E | 0-0 | 24-11-21 | D04630J | 15 | | | D04034J | 15 | | | ALL | |
| 301B | 18 | PC | K | 46-3 | 24-21-21 | D04036J | 1 | | | D04400J | 1 | | | 050-099 | |
| 301B | 18 | PC | K | 56-4 | 24-21-21 | D04036J | 1 | | | D04400J | 1 | | | 150-154, 162-163, 275-276 | |
| 301B | 18 | PC | K | 63-4 | 24-21-21 | D04036J | 1 | | | D04400J | 1 | | | 155-157, 164-199, 277-299 | |
| 301R | 18 | PC | K | 0-0 | 24-21-21 | D04036J | 2 | | | D04400J | 2 | | | ALL | |
| 301Y | 18 | PC | K | 0-0 | 24-21-21 | D04036J | 3 | | | D04400J | 3 | | | ALL | |
| 302B | 18 | PC | J | 15-2 | 24-21-21 | D04036J | 9 | | | D04062P | 12 | | | ALL | |
| 302R | 18 | PC | J | 0-0 | 24-21-21 | D04036J | 10 | | | D04062P | 13 | | | ALL | |
| 302Y | 18 | PC | J | 0-0 | 24-21-21 | D04036J | 11 | | | D04062P | 14 | | | ALL | |
| 401B | 24 | PN | C | 46-0 | 24-21-21 | D04630J | 8 | | | D04034J | 8 | | | 050-099 | |
| 401B | 24 | PN | C | 56-1 | 24-21-21 | D04630J | 8 | | | D04034J | 8 | | | 150-154, 162-163, 275-276 | |
| 401B | 24 | PN | C | 63-4 | 24-21-21 | D04630J | 8 | | | D04034J | 8 | | | 155-157, 164-199, 277-299 | |
| 401G | 24 | PN | C | 0-0 | 24-21-21 | D04630J | 11 | | | D04034J | 11 | | | ALL | |
| 401R | 24 | PN | C | 0-0 | 24-21-21 | D04630J | 9 | | | D04034J | 9 | | | ALL | |
| 401Y | 24 | PN | C | 0-0 | 24-21-21 | D04630J | 10 | | | D04034J | 10 | | | ALL | |
| 402B | 24 | PN | F | 25-2 | 24-23-11 | D04078J | 1 | | | D04794P | 19 | | | ALL | |
| 402G | 24 | PN | F | 0-0 | 24-23-11 | D04078J | 4 | | | D04794P | 22 | | | ALL | |
| 402R | 24 | PN | F | 0-0 | 24-23-11 | D04078J | 2 | | | D04794P | 20 | | | ALL | |
| 402Y | 24 | PN | F | 0-0 | 24-23-11 | D04078J | 3 | | | D04794P | 21 | | | ALL | |
| 403B | 24 | PN | G | 14-9 | 24-23-11 | D04078J | 5 | | | D04012P | 24 | | | ALL | |
| 403G | 24 | PN | G | 0-0 | 24-23-11 | D04078J | 8 | | | D04012P | 27 | | | ALL | |
| 403R | 24 | PN | G | 0-0 | 24-23-11 | D04078J | 6 | | | D04012P | 25 | | | ALL | |
| 403Y | 24 | PN | G | 0-0 | 24-23-11 | D04078J | 7 | | | D04012P | 26 | | | ALL | |
| 404B | 24 | PN | H | 14-9 | 24-23-11 | D04078J | 9 | | | D04012P | 28 | | | ALL | |
| 404G | 24 | PN | H | 0-0 | 24-23-11 | D04078J | 12 | | | D04012P | 31 | | | ALL | |
| 404R | 24 | PN | H | 0-0 | 24-23-11 | D04078J | 10 | | | D04012P | 29 | | | ALL | |
| 404Y | 24 | PN | H | 0-0 | 24-23-11 | D04078J | 11 | | | D04012P | 30 | | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0220
Page 6
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|--|-------|-------|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0222 | 286T0222 | P4 TO R W/B DISCONNECT-R2-R IDG CONTROL (continued) | | | | | | | | | | | | | | | | |
| 603 | 20 | | PA | 22-10 | 33-24-14 | D10926 | | | | 3 | | | | SP03902 | | S | | 050-099, 150-199 |
| 604 | 20 | | PA | 22-10 | 33-24-14 | D10926 | | | | 1 | | | | SP03904 | | S | | 050-099, 150-199 |
| 605 | 20 | | PA | 1-10 | 33-24-14 | D10926 | | | | 2 | | | | GD01820 | A.. | G | | 050-099, 150-199 |
| 627 | 20 | | PA | 13-9 | 33-24-13 | D10932 | | | | 7 | | | | SP02206 | | 9 | | 280-299 |
| 628 | 20 | | PA | 13-9 | 33-24-13 | D10932 | | | | 5 | | | | SP02208 | | 9 | | 280-299 |
| 629 | 20 | | PA | 15-4 | 33-24-13 | D10932 | | | | 6 | | | | GD04192 | A.. | 2 | | 280-299 |
| W0223 | 286T0223 | PWR DIST C,P11 TO SHELVES | | | | | | | | | | | | | | | | |
| 001 | 20 | | PA | 35-0 | 22-11-32 | D05187P | | | | 1 | | | | D04225J | | 1 | | ALL |
| 002 | 20 | | PA | 35-0 | SPARE | D05187P | | | | 2 | | | | D04225J | | 2 | | ALL |
| 003 | 20 | | PA | 35-0 | 22-11-31 | D05187P | | | | 3 | | | | D04225J | | 3 | | ALL |
| 004 | 20 | | PA | 35-0 | SPARE | D05187P | | | | 4 | | | | D04225J | | 4 | | ALL |
| 005 | 22 | | PA | 35-0 | SPARE | D05187P | | | | 5 | | | | D04225J | | 5 | | ALL |
| 006 | 24 | | PK | 38-0 | 34-21-31 | D05187P | | | | 6 | | | | D04293J | | 1 | | ALL |
| 007 | 22 | | PA | 38-0 | SPARE | D05187P | | | | 7 | | | | D04293J | | 2 | | ALL |
| 008 | 22 | | PA | 38-0 | SPARE | D05187P | | | | 8 | | | | D04293J | | 3 | | ALL |
| 009 | 20 | | PA | 61-0 | 34-33-31 | D05187P | | | | 9 | | | | D05189J | | 2 | | ALL |
| 010 | 22 | | PA | 61-0 | SPARE | D05187P | | | | 10 | | | | D05189J | | 3 | | ALL |
| 011 | 22 | | PA | 61-0 | SPARE | D05187P | | | | 11 | | | | D05189J | | 1 | | ALL |
| W0226 | 286T0226 | P31-A2-L1-L AFT GALLEY POWER FEEDER | | | | | | | | | | | | | | | | |
| 005 | 04 | | HA | 25-0 | 25-31-21 | D00590 | | | | A | | | | TB0253 | | 1 | F | 050-099 |
| 005 | 04 | | HA | 26-1 | 25-31-21 | D00590 | | | | A | | | | TB0253 | | 1 | F | 150-199 |
| 005 | 06 | | HA | 5-11 | 25-31-21 | D00590 | | | | A | | | | SM00001 | | | GF | 275-299 |
| 006 | 04 | | HA | 25-0 | 25-31-21 | D00590 | | | | B | | | | TB0253 | | 2 | F | 050-099 |
| 006 | 04 | | HA | 26-1 | 25-31-21 | D00590 | | | | B | | | | TB0253 | | 2 | F | 150-199 |
| 006 | 06 | | HA | 5-11 | 25-31-21 | D00590 | | | | B | | | | SM00002 | | | GF | 275-299 |
| 007 | 04 | | HA | 25-0 | 25-31-21 | D00590 | | | | C | | | | TB0253 | | 3 | F | 050-099 |
| 007 | 04 | | HA | 26-1 | 25-31-21 | D00590 | | | | C | | | | TB0253 | | 3 | F | 150-199 |
| 007 | 06 | | HA | 5-11 | 25-31-21 | D00590 | | | | C | | | | SM00003 | | | GF | 275-299 |
| 008 | 04 | | HA | 2-0 | 25-31-21 | D00590 | | | | D | | | | GD01822 | A.. | G | | 050-099 |
| 008 | 04 | | HA | 2-9 | 25-31-21 | D00590 | | | | D | | | | GD01822 | A.. | G | | 150-199 |
| 008 | 06 | | HA | 1-7 | 25-31-21 | D00590 | | | | D | | | | GD01822 | A.. | G | | 275-299 |
| 009 | 02 | | QY | 114-0 | 25-31-21 | M01636 | | | A2 | H2 | | | | TB0253 | | 1 | F2 | 050-099 |
| 009 | 02 | | QY | 135-3 | 25-31-21 | M01636 | | | A2 | H2 | | | | TB0253 | | 1 | F2 | 150-199 |
| 009 | 04 | | QY | 149-6 | 25-31-21 | M00227 | | | A2 | H4 | | | | SM00001 | | | GF | 275-299 |
| 010 | 02 | | QY | 114-0 | 25-31-21 | M01636 | | | B2 | H2 | | | | TB0253 | | 2 | F2 | 050-099 |
| 010 | 02 | | QY | 135-6 | 25-31-21 | M01636 | | | B2 | H2 | | | | TB0253 | | 2 | F2 | 150-199 |
| 010 | 04 | | QY | 149-6 | 25-31-21 | M00227 | | | B2 | H4 | | | | SM00002 | | | GF | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0220

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0226 | 286T0226 | | | P31-A2-L1-L AFT GALLEY POWER FEEDER (continued) | | | | | | | | | | | |
| 011 | 02 | | QY | | 115-0 | 25-31-21 | M01636 | C2 | H2 | | TB0253 | 3 | F2 | | 050-099 |
| 011 | 02 | | QY | | 135-8 | 25-31-21 | M01636 | C2 | H2 | | TB0253 | 3 | F2 | | 150-199 |
| 011 | 04 | | QY | | 149-6 | 25-31-21 | M00227 | C2 | H4 | | SM00003 | | GF | | 275-299 |
| 019 | 16 | | PA | | 34-2 | 25-31-21 | D12100 | | 3 | | D02178 | 3 | | | 275-278 |
| 019 | 16 | | PA | | 35-0 | 25-31-21 | D12100 | | 3 | | D02178 | 3 | | | 280-299 |
| 026 | 16 | | PA | | 34-2 | 25-31-21 | D12100 | | 4 | | D02178 | 4 | | | 275-278 |
| 026 | 16 | | PA | | 35-0 | 25-31-21 | D12100 | | 4 | | D02178 | 4 | | | 280-299 |
| 027 | 16 | | PA | | 34-2 | 25-31-21 | D12100 | | 5 | | D02178 | 5 | | | 275-278 |
| 027 | 16 | | PA | | 35-0 | 25-31-21 | D12100 | | 5 | | D02178 | 5 | | | 280-299 |
| 028 | 16 | | PA | | 34-2 | 25-31-21 | D12100 | | 6 | | D02178 | 6 | | | 275-278 |
| 028 | 16 | | PA | | 35-0 | 25-31-21 | D12100 | | 6 | | D02178 | 6 | | | 280-299 |
| 029 | 16 | | PA | | 34-2 | 25-31-21 | D12100 | | 7 | | D02178 | 7 | | | 275-278 |
| 029 | 16 | | PA | | 35-0 | 25-31-21 | D12100 | | 7 | | D02178 | 7 | | | 280-299 |
| 030 | 16 | | PA | | 34-2 | 25-31-21 | D12100 | | 8 | | D02178 | 8 | | | 275-278 |
| 030 | 16 | | PA | | 35-0 | 25-31-21 | D12100 | | 8 | | D02178 | 8 | | | 280-299 |
| 031 | 16 | | PA | | 34-2 | 25-31-21 | D12100 | | 9 | | D02178 | 9 | | | 275-278 |
| 031 | 16 | | PA | | 35-0 | 25-31-21 | D12100 | | 9 | | D02178 | 9 | | | 280-299 |
| 032 | 16 | | PA | | 34-2 | 25-31-21 | D12100 | | 10 | | D02178 | 10 | | | 275-278 |
| 032 | 16 | | PA | | 35-0 | 25-31-21 | D12100 | | 10 | | D02178 | 10 | | | 280-299 |
| 033 | 16 | | PA | | 34-2 | 25-31-21 | D12100 | | 11 | | D02178 | 11 | | | 275-278 |
| 033 | 16 | | PA | | 35-0 | 25-31-21 | D12100 | | 11 | | D02178 | 11 | | | 280-299 |
| 034 | 16 | | PA | | 34-2 | 25-31-21 | D12100 | | 12 | | D02178 | 12 | | | 275-278 |
| 034 | 16 | | PA | | 35-0 | 25-31-21 | D12100 | | 12 | | D02178 | 12 | | | 280-299 |
| 035 | 16 | | PA | | 34-2 | 25-31-21 | D12100 | | 13 | | D02178 | 13 | | | 275-278 |
| 035 | 16 | | PA | | 35-0 | 25-31-21 | D12100 | | 13 | | D02178 | 13 | | | 280-299 |
| 036 | 16 | | PA | | 34-2 | 25-31-21 | D12100 | | 14 | | D02178 | 14 | | | 275-278 |
| 036 | 16 | | PA | | 35-0 | 25-31-21 | D12100 | | 14 | | D02178 | 14 | | | 280-299 |
| 037 | 16 | | PA | | 34-2 | 25-31-21 | D12210 | | 3 | | D12212 | 3 | | | 275-299 |
| 038 | 16 | | PA | | 34-2 | 25-31-21 | D12210 | | 4 | | D12212 | 4 | | | 275-299 |
| 039 | 16 | | PA | | 34-2 | 25-31-21 | D12210 | | 5 | | D12212 | 5 | | | 275-299 |
| 040 | 16 | | PA | | 34-2 | 25-31-21 | D12210 | | 6 | | D12212 | 6 | | | 275-299 |
| 041 | 16 | | PA | | 34-2 | 25-31-21 | D12210 | | 7 | | D12212 | 7 | | | 275-299 |
| 042 | 16 | | PA | | 34-2 | 25-31-21 | D12210 | | 8 | | D12212 | 8 | | | 275-299 |
| 043 | 16 | | PA | | 34-2 | 25-31-21 | D12210 | | 9 | | D12212 | 9 | | | 275-299 |
| 044 | 16 | | PA | | 34-2 | 25-31-21 | D12210 | | 10 | | D12212 | 10 | | | 275-299 |
| 045 | 16 | | PA | | 34-2 | 25-31-21 | D12210 | | 11 | | D12212 | 11 | | | 275-299 |
| 046 | 16 | | PA | | 34-2 | 25-31-21 | D12210 | | 12 | | D12212 | 12 | | | 275-299 |
| 047 | 16 | | PA | | 34-2 | 25-31-21 | D12210 | | 13 | | D12212 | 13 | | | 275-299 |
| 048 | 16 | | PA | | 34-2 | 25-31-21 | D12210 | | 14 | | D12212 | 14 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0220

Page 8 End

Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|---|----|-------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0230 | 286T0230 | P34 TO P32 TO P31-A1-AC TIE BUS & GROUND POWER BUS | | | | | | | | | | | | | | |
| 001 | 04 | HA | | 17-0 | 24-21-51 | C00902 | | L1 | H | | C00904 | L1 | H | *1 | ALL | |
| 002 | 04 | HA | | 17-0 | 24-21-51 | C00902 | | L2 | H | | C00904 | L2 | H | *2 | ALL | |
| 003 | 04 | HA | | 17-0 | 24-21-51 | C00902 | | L3 | H | | C00904 | L3 | H | *3 | ALL | |
| 004 | 04 | HA | | 17-0 | 24-21-51 | C00905 | | L1 | H | *1 | C00904 | L1 | H | *1 | ALL | |
| 005 | 04 | HA | | 17-0 | 24-21-51 | C00905 | | L2 | H | *2 | C00904 | L2 | H | *2 | ALL | |
| 006 | 04 | HA | | 17-0 | 24-21-51 | C00905 | | L3 | H | *3 | C00904 | L3 | H | *3 | ALL | |
| 007 | 04 | HA | | 3-0 | 24-21-51 | C00905 | | L1 | H | *1 | K00114 | A2 | H | | ALL | |
| 008 | 04 | HA | | 3-0 | 24-21-51 | C00905 | | L2 | H | *2 | K00114 | B2 | H | | ALL | |
| 009 | 04 | HA | | 2-6 | 24-21-51 | C00905 | | L3 | H | *3 | K00114 | C2 | H | | ALL | |
| 010 | 08 | PA | | 17-0 | 24-51-52 | K00103 | | A2 | F | | K00102 | A1 | F | | ALL | |
| 011 | 08 | PA | | 17-0 | 24-51-52 | K00103 | | B2 | F | | K00102 | B1 | F | | ALL | |
| 012 | 08 | PA | | 17-0 | 24-51-52 | K00103 | | C2 | F | | K00102 | C1 | F | | ALL | |
| 013 | 04 | HA | | 19-6 | 24-21-51 | C00902 | | L1 | H | | K00114 | A2 | H | | ALL | |
| 014 | 04 | HA | | 20-6 | 24-21-51 | C00902 | | L2 | H | | K00114 | B2 | H | | ALL | |
| 015 | 04 | HA | | 19-6 | 24-21-51 | C00902 | | L3 | H | | K00114 | C2 | H | | ALL | |
| W0232 | 286T0232 | P30 TO P34-A1-EXTERNAL POWER BUS FEEDER | | | | | | | | | | | | | | |
| 001 | *1 | PA | | 9-2 | 24-41-11 | D00372 | | A | H | | K00114 | A1 | H | | ALL | |
| 002 | *1 | PA | | 7-9 | 24-41-11 | D00372 | | B | H | | K00114 | B1 | H | | ALL | |
| 003 | *1 | PA | | 7-9 | 24-41-11 | D00372 | | C | H | | K00114 | C1 | H | | ALL | |
| 004 | *1 | PA | | 3-2 | 24-41-11 | D00372 | | N | H | | GD00018 | A.. | H | | ALL | |
| W0236 | 286T0236 | P34 TO APU FIREWALL DISCONNECT-A1-APU GENERATOR POWER FEEDER | | | | | | | | | | | | | | |
| 001 | *2 | QY | | 131-0 | 24-21-41 | C00905 | | T1 | H* | | SM00001 | | GJ | | 050-099 | |
| 001 | *2 | QY | | 151-0 | 24-21-41 | C00905 | | T1 | H* | | SM00001 | | GJ | | 150-199, 275-299 | |
| 002 | *2 | QY | | 131-0 | 24-21-41 | C00905 | | T2 | H* | | SM00002 | | GJ | | 050-099 | |
| 002 | *2 | QY | | 151-0 | 24-21-41 | C00905 | | T2 | H* | | SM00002 | | GJ | | 150-199, 275-299 | |
| 003 | *2 | QY | | 131-0 | 24-21-41 | C00905 | | T3 | H* | | SM00003 | | GJ | | 050-099 | |
| 003 | *2 | QY | | 151-0 | 24-21-41 | C00905 | | T3 | H* | | SM00003 | | GJ | | 150-199, 275-299 | |
| 004 | *1 | HA | | 9-0 | 24-21-41 | SM00001 | | | GJ | | M00281 | T1 | RA | | 050-099, 150-199, 275-278 | |
| 004 | *1 | HA | | 4-0 | 24-21-41 | SM00001 | | | GJ | | M00281 | T1 | RA | | 280-299 | |
| 005 | *1 | HA | | 9-0 | 24-21-41 | SM00002 | | | GJ | | M00281 | T2 | RA | | 050-099, 150-199, 275-278 | |
| 005 | *1 | HA | | 4-0 | 24-21-41 | SM00002 | | | GJ | | M00281 | T2 | RA | | 280-299 | |
| 006 | *1 | HA | | 9-0 | 24-21-41 | SM00003 | | | GJ | | M00281 | T3 | RA | | 050-099, 150-199, 275-278 | |
| 006 | *1 | HA | | 4-0 | 24-21-41 | SM00003 | | | GJ | | M00281 | T3 | RA | | 280-299 | |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0236 | 286T0236 | | | P34 TO APU FIREWALL DISCONNECT-A1-APU GENERATOR POWER FEEDER (continued) | | | | | | | | | | | |
| 007 | 04 | | HA | 7-0 | 24-21-41 | GD01298 | A.. | H7 | | M00281 | | N | RB | | 050-099, 150-199, 275-278 |
| 007 | 04 | | HA | 4-0 | 24-21-41 | GD01298 | A.. | H7 | | M00281 | | N | RB | | 280-299 |
| W0238 | 286T0238 | | | P33-TO-E6-R1-GND SVCE PWR | | | | | | | | | | | |
| 001 | 18 | | PA | 113-0 | 24-31-41 | D04134P | | | 1 | D04130J | | 1 | | | 050-099 |
| 001 | 18 | | PA | 135-0 | 24-31-41 | D04134P | | | 1 | D04130J | | 1 | | | 150-199, 275-299 |
| 002 | 18 | | PA | 113-0 | 24-31-41 | D04134P | | | 2 | D04130J | | 2 | | | 050-099 |
| 002 | 18 | | PA | 135-0 | 24-31-41 | D04134P | | | 2 | D04130J | | 2 | | | 150-199, 275-299 |
| 003 | 18 | | PA | 113-0 | 24-31-41 | D04134P | | | 3 | D04130J | | 3 | | | 050-099 |
| 003 | 18 | | PA | 135-0 | 24-31-41 | D04134P | | | 3 | D04130J | | 3 | | | 150-199, 275-299 |
| 008 | 06 | | QY | 126-0 | 24-32-41 | TB5034 | | | 3 | E/ | SM00004 | | | GE | 275-299 |
| 009 | 06 | | QY | 126-0 | 24-32-41 | TB5034 | | | 2 | E/ | SM00005 | | | GE | 275-299 |
| 010 | 06 | | QY | 126-0 | 24-32-41 | TB5034 | | | 1 | E/ | SM00006 | | | GE | 275-299 |
| 011 | 08 | | PA | 3-0 | 24-32-41 | K00618 | | A1 | E | SM00006 | | | | GE | 275-278 |
| 011 | 08 | | PA | 3-6 | 24-32-41 | K00618 | | A1 | E | SM00006 | | | | GE | 280-299 |
| 012 | 08 | | PA | 3-0 | 24-32-41 | K00618 | | B1 | E | SM00005 | | | | GE | 275-278 |
| 012 | 08 | | PA | 3-6 | 24-32-41 | K00618 | | B1 | E | SM00005 | | | | GE | 280-299 |
| 013 | 08 | | PA | 3-0 | 24-32-41 | K00618 | | C1 | E | SM00004 | | | | GE | 275-278 |
| 013 | 08 | | PA | 3-6 | 24-32-41 | K00618 | | C1 | E | SM00004 | | | | GE | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0230
Page 2 End
Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0240 | 286T0240 | | | P61 TO P34-A2-APU/EXT PWR CONTROL | | | | | | | | | | | |
| 001 | 24 | | PK | 26-0 | 24-22-41 | D04048J | | 1 | | | D04796P | | 1 | | ALL |
| 002 | 24 | | PK | 26-0 | 24-22-41 | D04048J | | 2 | | | D04796P | | 2 | | ALL |
| 004 | 24 | | PK | 22-0 | 24-51-71 | D04052P | | 8 | | | D04048J | | 3 | | ALL |
| 006 | 20 | | PA | 26-0 | 24-22-41 | D04048J | | 8 | | | D04796P | | 8 | | ALL |
| 007 | 20 | | PA | 26-0 | 24-22-41 | D04048J | | 9 | | | D04796P | | 9 | | ALL |
| 008 | 20 | | PA | 26-0 | 24-22-41 | D04048J | | 10 | | | D04796P | | 10 | | ALL |
| 009 | 24 | | PK | 26-0 | 24-41-11 | D04048J | | 11 | | | D04796P | | 11 | | ALL |
| 010 | 20 | | PQ | M | 26-0 | 24-41-11 | D04048J | | 12 | | D04796P | | 12 | | ALL |
| 010Z | | | | M | 0-0 | 24-41-11 | D04048J | DED | | | D04796P | DED | | | ALL |
| 011 | 20 | | PQ | N | 26-0 | 24-41-11 | D04048J | | 13 | | D04796P | | 13 | | ALL |
| 011Z | | | | N | 0-0 | 24-41-11 | D04048J | DED | | | D04796P | DED | | | ALL |
| 012 | 20 | | PA | | 26-0 | SPARE | D04048J | | 14 | | D04796P | | 14 | | ALL |
| 013 | 20 | | PA | | 26-0 | SPARE | D04048J | | 15 | | D04796P | | 15 | | ALL |
| 014 | 16 | | PA | | 40-0 | 30-71-25 | D04026P | | 7 | | D04052P | FL | 7 | | 050-099, 150-199 |
| 019 | 24 | | PK | | 25-0 | 24-41-12 | D04112P | | 21 | | D04796P | | 21 | | ALL |
| 021 | 22 | | PA | | 25-0 | 49-61-11 | D04112P | | 25 | | D04796P | | 25 | | ALL |
| 022 | 22 | | PA | | 25-0 | 49-61-11 | D04112P | | 26 | | D04796P | | 26 | | ALL |
| 023 | 22 | | PA | | 25-0 | 49-61-11 | D04112P | | 27 | | D04796P | | 27 | | ALL |
| 024 | 22 | | PA | | 25-0 | 49-61-11 | D04112P | | 28 | | D04796P | | 28 | | ALL |
| 025 | 22 | | PA | | 25-0 | 49-61-11 | D04112P | | 29 | | D04796P | | 29 | | ALL |
| 033 | 18 | | PA | | 26-0 | 24-22-41 | D04026P | | 1 | | D04114J | | 1 | | ALL |
| 034 | 24 | | PK | | 26-0 | 24-22-41 | D04112P | | 1 | | D04048J | | 16 | | ALL |
| 035 | 24 | | PK | | 26-0 | 24-41-11 | D04112P | | 2 | | D04048J | | 17 | | ALL |
| 036 | 24 | | PK | | 26-0 | 24-41-11 | D04112P | | 3 | | D04048J | | 18 | | ALL |
| 037 | 24 | | PK | | 26-0 | 24-41-11 | D04112P | | 4 | | D04048J | | 19 | | ALL |
| 038 | 24 | | PK | | 26-0 | 24-41-11 | D04112P | | 5 | | D04048J | | 20 | | ALL |
| 039 | 24 | | PK | | 26-0 | 24-41-11 | D04112P | | 6 | | D04048J | | 21 | | ALL |
| 040 | 24 | | PK | | 22-0 | 24-51-71 | D04052P | | 6 | | D04048J | | 22 | | ALL |
| 041 | 24 | | PK | | 22-0 | 24-51-71 | D04052P | | 5 | | D04048J | | 23 | | ALL |
| 042 | 24 | | PK | | 26-0 | 24-27-21 | D04112P | | 9 | | D04048J | | 24 | | ALL |
| 043 | 20 | | PA | | 26-0 | 24-22-41 | D04112P | | 10 | | D04048J | | 25 | | ALL |
| 044 | 20 | | PA | | 26-0 | 24-22-41 | D04112P | | 11 | | D04048J | | 26 | | ALL |
| 045 | 20 | | PA | | 26-0 | 24-22-41 | D04112P | | 12 | | D04048J | | 27 | | ALL |
| 046 | 20 | | PA | | 26-0 | 24-41-11 | D04112P | | 13 | | D04048J | | 28 | | ALL |
| 047 | 24 | | PK | | 26-0 | 24-51-61 | D04112P | | 14 | | D04048J | | 29 | | ALL |
| 048 | 24 | | PK | | 26-0 | 24-51-61 | D04112P | | 15 | | D04048J | | 30 | | ALL |
| 049 | 24 | | PK | | 26-0 | 24-51-51 | D04112P | | 36 | | D04048J | | 31 | | ALL |
| 050 | 24 | | PK | | 25-0 | 24-22-41 | D04796P | | 36 | | D04048J | | 40 | | ALL |
| 052 | 24 | | PK | | 26-0 | 24-51-71 | D04112P | | 48 | | D04048J | | 45 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0240

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|--|----|-------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0240 | 286T0240 | P61 TO P34-A2-APU/EXT PWR CONTROL (continued) | | | | | | | | | | | | | |
| 053 | 24 | | PK | 22-0 | 24-51-71 | D04052P | | 10 | | | D04048J | | 46 | | ALL |
| 054 | 22 | | PA | 25-0 | 49-61-11 | D04112P | | 49 | | | D04796P | | 31 | | ALL |
| 056 | 24 | | PK | 26-0 | 24-51-71 | D04048J | | 6 | | | D04112P | | 47 | | ALL |
| 057 | 24 | | PK | 25-0 | 24-41-11 | D04112P | | 53 | | | D04796P | | 45 | | ALL |
| 058 | 24 | | PK | 26-0 | 24-41-11 | D04112P | | 54 | | | D04048J | | 52 | | ALL |
| 059 | 20 | | PA | 25-10 | 24-22-22 | D04026P | | 5 | | | D04048J | | 48 | | ALL |
| 060 | 20 | | PA | 25-10 | 24-22-22 | D04026P | | 6 | | | D04048J | | 49 | | ALL |
| 065 | 20 | | PA | 25-0 | 24-32-41 | D04112P | | 22 | | | D04796P | | 22 | | 275-299 |
| 070 | 20 | | PA | 25-0 | SPARE | D04796P | | 53 | | | D04048J | | 53 | | ALL |
| 071 | 20 | | PA | 25-0 | SPARE | D04796P | | 54 | | | D04048J | | 54 | | ALL |
| 072 | 24 | | PK | 26-0 | 24-22-41 | D04796P | | 43 | | | D04048J | | 51 | | ALL |
| 073 | 24 | | PK | 26-0 | 24-41-11 | D04796P | | 44 | | | D04048J | | 4 | | ALL |
| 074 | 24 | | PK | 25-0 | 24-27-41 | D04796P | | 46 | | | D04112P | | 31 | | ALL |
| 075 | 24 | | PK | 25-0 | 24-27-41 | D04796P | | 47 | | | D04112P | | 32 | | ALL |
| 076 | 22 | | PA | 25-0 | SPARE | D04796P | | 41 | | | D04112P | | 30 | | ALL |
| 301B | 18 | | PC | D | 26-0 | 24-21-41 | D04026P | | 2 | | D04114J | | 2 | | ALL |
| 301R | 18 | | PC | D | 0-0 | 24-21-41 | D04026P | | 3 | | D04114J | | 3 | | ALL |
| 301Y | 18 | | PC | D | 0-0 | 24-21-41 | D04026P | | 4 | | D04114J | | 4 | | ALL |
| 401B | 24 | | PN | B | 26-0 | 24-23-11 | D04112P | | 37 | | D04048J | | 32 | | ALL |
| 401G | 24 | | PN | B | 0-0 | 24-23-11 | D04112P | | 38 | | D04048J | | 33 | | ALL |
| 401R | 24 | | PN | B | 0-0 | 24-23-11 | D04112P | | 39 | | D04048J | | 34 | | ALL |
| 401Y | 24 | | PN | B | 0-0 | 24-23-11 | D04112P | | 40 | | D04048J | | 35 | | ALL |
| 402B | 24 | | PN | C | 26-0 | 24-41-11 | D04112P | | 41 | | D04048J | | 36 | | ALL |
| 402G | 24 | | PN | C | 0-0 | 24-41-11 | D04112P | | 42 | | D04048J | | 37 | | ALL |
| 402R | 24 | | PN | C | 0-0 | 24-41-11 | D04112P | | 43 | | D04048J | | 38 | | ALL |
| 402Y | 24 | | PN | C | 0-0 | 24-41-11 | D04112P | | 44 | | D04048J | | 39 | | ALL |
| 403B | 24 | | PN | H | 22-0 | 24-23-12 | D04052P | | 1 | | D04048J | | 41 | | ALL |
| 403G | 24 | | PN | H | 0-0 | 24-23-12 | D04052P | | 2 | | D04048J | | 42 | | ALL |
| 403R | 24 | | PN | H | 0-0 | 24-23-12 | D04052P | | 3 | | D04048J | | 43 | | ALL |
| 403Y | 24 | | PN | H | 0-0 | 24-23-12 | D04052P | | 4 | | D04048J | | 44 | | ALL |
| 801 | 20 | | PA | 26-0 | SPARE | D04796P | | 55 | | | D04048J | | 55 | | ALL |
| W0241 | 286T0241 | HF-L COAX,SHELF TO TAIL DISC | | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-11-11 | D04001J | | = C1 | | | D04003P | | = C1 | | ALL |
| 01CX | | | BS | A | 123-0 | 23-11-11 | D04001J | | = A1 | | D04003P | | = A1 | | 050-099 |
| 01CX | | | BS | A | 145-0 | 23-11-11 | D04001J | | = A1 | | D04003P | | = A1 | | 150-199, 275-299 |
| W0242 | 286T0242 | E6 TO APU FWD-A2-APU CONTROL | | | | | | | | | | | | | |
| 001 | 20 | | UA | 40-0 | 49-14-11 | D04082J | | 35 | | | D04024J | | 6 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0240
Page 2
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0242 | 286T0242 | | | E6 TO APU FWD-A2-APU CONTROL (continued) | | | | | | | | | | | | | | |
| 002 | 20 | | UA | 40-0 | 49-14-11 | D04082J | | 36 | | | | | D04024J | | 5 | | | ALL |
| 003 | 20 | | UA | 40-0 | 49-14-11 | D04082J | | 37 | | | | | D04024J | | 8 | | | ALL |
| 004 | 20 | | UA | 40-0 | 49-14-11 | D04082J | | 38 | | | | | D04024J | | 16 | | | ALL |
| 005 | 20 | | UA | 40-0 | 49-14-11 | D04082J | | 39 | | | | | D04024J | | 7 | | | ALL |
| 006 | 20 | | UA | 49-1 | 36-11-41 | D04082J | | 7 | | | | | D00560 | | 4 | | | ALL |
| 007 | 20 | | UA | 49-1 | 36-11-41 | D04082J | | 8 | | | | | D00560 | | 7 | | | ALL |
| 008 | 20 | | UA | 40-0 | 49-14-11 | D04082J | | 42 | | | | | D04024J | | 2 | | | ALL |
| 009 | 20 | | UA | 40-0 | 49-14-11 | D04082J | | 43 | | | | | D04024J | | 3 | | | ALL |
| 010 | 20 | | UA | 40-0 | 49-14-11 | D04082J | | 44 | | | | | D04024J | | 1 | | | ALL |
| 011 | 20 | | UA | 40-0 | 49-14-11 | D04082J | | 45 | | | | | D04024J | | 19 | | | ALL |
| 013 | 20 | | UA | 3-6 | 49-14-11 | D04024J | | 4 | | | | | GD01628 | D.. | N | | | ALL |
| 014 | 20 | | UA | 3-6 | 49-14-11 | D04024J | | 17 | | | | | GD01628 | D.. | N | | | ALL |
| 015 | 20 | | UA | 40-0 | 49-14-11 | D04024J | | 20 | | | | | D04082J | | 34 | | | ALL |
| 016 | 20 | | UA | 3-6 | 49-94-11 | D04024J | | 15 | | | | | GD01628 | D.. | N | | | 150-199 |
| 017 | 20 | | UA | 44-2 | 49-15-11 | D04082J | | 47 | | | | | SP01510 | | 9 | | | ALL |
| 018 | 16 | | UA | 39-9 | 49-15-11 | D04082J | | 48 | FL | | | | D00502 | | 5 | | | ALL |
| 019 | 16 | | UA | 39-9 | 49-15-11 | D04082J | | 49 | FL | | | | D00502 | | 7 | | | ALL |
| 020 | 20 | | UA | 39-9 | 49-15-11 | D04082J | | 50 | | | | | D00502 | | 1 | | | ALL |
| 021 | 20 | | UA | 39-9 | 49-15-11 | D04082J | | 51 | | | | | D00502 | | 10 | | | ALL |
| 022 | 16 | | UA | 2-2 | 49-15-11 | D00502 | | 3 | | | | | GD01632 | S.. | N | | | ALL |
| 023 | 20 | | UA | 2-0 | 49-15-11 | D00502 | | 4 | | | | | GD01634 | D.. | N | | | ALL |
| 024 | 16 | | UA | 2-0 | 49-15-11 | D00502 | | 6 | | | | | GD01634 | D.. | N | | | ALL |
| 025 | 20 | | UA | 2-0 | 49-15-11 | D00502 | | 8 | | | | | GD01634 | D.. | N | | | ALL |
| 026 | 18 | | UA | 14-5 | 33-31-31 | S00427 | | 2 | L | | | | SM00001 | | 9 | | | ALL |
| 027 | 18 | | UA | 9-1 | 33-31-31 | S00427 | | 3 | L | | | | SP00612 | | 9 | | | ALL |
| 028 | 18 | | UA | 4-4 | 33-31-31 | S00443 | | 2 | L | | | | SM00001 | | 9 | | | ALL |
| 029 | 18 | | UA | 9-5 | 33-31-31 | S00443 | | 3 | L | | | | SP00614 | | 9 | | | ALL |
| 030 | 18 | | UA | 2-2 | 33-31-31 | D04018J | | 1 | | | | | SM00001 | | 9 | | | ALL |
| 031 | 18 | | UA | 5-5 | 33-31-31 | D02662 | | 5 | | | | | SM00001 | | 9 | | | ALL |
| 032 | 18 | | UA | 3-3 | 33-31-31 | D02662 | | 6 | | | | | GD03638 | S.. | N | | | ALL |
| 033 | 18 | | UA | 3-3 | 33-31-31 | D02662 | | 1 | | | | | GD01630 | A.. | N | | | ALL |
| 034 | 18 | | UA | 43-4 | 33-31-31 | D04040J | | 1 | DK | | | | D02662 | | 3 | | | ALL |
| 035 | 18 | | UA | 4-8 | 36-11-41 | D00560 | | 3 | | | | | GD03588 | A.. | N | | | ALL |
| 036 | 18 | | UA | 4-8 | 36-11-41 | D00560 | | 5 | | | | | GD03586 | D.. | N | | | ALL |
| 037 | 18 | | UA | 4-8 | 36-11-41 | D00560 | | 6 | | | | | GD03586 | D.. | N | | | ALL |
| 038 | 20 | | UA | 39-9 | 49-15-11 | D04082J | | 46 | | | | | D00502 | | 2 | | | ALL |
| 039 | 20 | | UA | 40-0 | 49-14-11 | D04082J | | 23 | | | | | D04024J | | 9 | | | ALL |
| 040 | 20 | | UA | 3-6 | 49-14-11 | GD01628 | | D.. | N | | | | D04024J | | 10 | | | ALL |
| 041 | 20 | | UA | 40-0 | 49-14-11 | D04082J | | 31 | | | | | D04024J | | 13 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0240

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0242 | 286T0242 | | | E6 TO APU FWD-A2-APU CONTROL (continued) | | | | | | | | | | | | | |
| 050 | 20 | | UA | | 40-1 | SPARE | D04040J | | 13 | | | | D04024J | CAP | Y | | 150-199 |
| 050 | 20 | | UA | | 40-1 | SPARE | D04040J | | 13 | | | | D04024J | | | | 275-299 |
| 051 | 20 | | UA | | 40-1 | SPARE | D04040J | | 14 | | | | D04018J | | | | 050-099 |
| 052 | 20 | | UA | | 40-1 | SPARE | D04040J | | 15 | | | | D04018J | | | | ALL |
| 053 | 18 | | UA | | 40-2 | SPARE | D04040J | | 16 | DK | | | D04030J | | | | ALL |
| 055 | 20 | | UA | | 49-1 | 36-11-41 | D04082J | | 12 | | | | D00560 | | | | ALL |
| 056 | 20 | | UA | | 49-1 | 36-11-41 | D04082J | | 11 | | | | D00560 | | | | ALL |
| 057 | 20 | | UA | | 39-9 | 49-15-11 | D04082J | | 24 | | | | D00502 | | | | ALL |
| 201B | 20 | | VG | D | 40-1 | 49-14-11 | D04082J | | 13 | | | | D04030J | | | | ALL |
| 201R | 20 | | VG | D | 0-0 | 49-14-11 | D04082J | | 14 | | | | D04030J | | | | ALL |
| 201Z | | | | D | 0-0 | 49-14-11 | D04082J | | | | FA | | D04030J | DED | | | ALL |
| 202B | 20 | | VG | E | 40-1 | 49-14-11 | D04082J | | 15 | | | | D04030J | | | | ALL |
| 202R | 20 | | VG | E | 0-0 | 49-14-11 | D04082J | | 16 | | | | D04030J | | | | ALL |
| 202Z | | | | E | 0-0 | 49-14-11 | D04082J | | | | FA | | D04030J | | | FD | ALL |
| 203B | 20 | | VG | F | 40-1 | 49-14-11 | D04082J | | 17 | | | | D04030J | | | | ALL |
| 203R | 20 | | VG | F | 0-0 | 49-14-11 | D04082J | | 18 | | | | D04030J | | | | ALL |
| 203Z | | | | F | 0-0 | 49-14-11 | D04082J | | | | FA | | D04030J | DED | | | ALL |
| 204B | 20 | | VG | G | 40-1 | 49-14-11 | D04082J | | 19 | | | | D04030J | | | | ALL |
| 204R | 20 | | VG | G | 0-0 | 49-14-11 | D04082J | | 20 | | | | D04030J | | | | ALL |
| 204Z | | | | G | 0-0 | 49-14-11 | D04082J | | | | FB | | D04030J | DED | | | ALL |
| 205B | 20 | | VG | H | 40-1 | 49-14-11 | D04082J | | 21 | | | | D04030J | | | | ALL |
| 205R | 20 | | VG | H | 0-0 | 49-14-11 | D04082J | | 22 | | | | D04030J | | | | ALL |
| 205Z | | | | H | 0-0 | 49-14-11 | D04082J | | | | FB | | D04030J | DED | | | ALL |
| 206B | 20 | | VG | N | 40-1 | 24-21-41 | D04040J | | 5 | | | | D04018J | | | | ALL |
| 206R | 20 | | VG | N | 0-0 | 24-21-41 | D04040J | | 6 | | | | D04018J | | | | ALL |
| 206Z | | | | N | 0-0 | 24-21-41 | D04040J | | 7 | | | | D04018J | | | | ALL |
| 207B | 20 | | VG | Q | 40-1 | 49-14-11 | D04082J | | 1 | | | | D04030J | | | | ALL |
| 207R | 20 | | VG | Q | 0-0 | 49-14-11 | D04082J | | 2 | | | | D04030J | | | | ALL |
| 207Z | | | | Q | 0-0 | 49-14-11 | D04082J | | | | FA | | D04030J | | | FC | ALL |
| 208B | 20 | | VG | A | 40-1 | 49-14-11 | D04082J | | 3 | | | | D04030J | | | | ALL |
| 208R | 20 | | VG | A | 0-0 | 49-14-11 | D04082J | | 4 | | | | D04030J | | | | ALL |
| 208Z | | | | A | 0-0 | 49-14-11 | D04082J | | | | FA | | D04030J | | | FC | ALL |
| 209B | 20 | | VG | B | 40-1 | 49-14-11 | D04082J | | 5 | | | | D04030J | | | | ALL |
| 209R | 20 | | VG | B | 0-0 | 49-14-11 | D04082J | | 6 | | | | D04030J | | | | ALL |
| 209Z | | | | B | 0-0 | 49-14-11 | D04082J | | | | FA | | D04030J | | | | ALL |
| 210B | 20 | | VG | C | 40-1 | 49-14-11 | D04082J | | 9 | | | | D04030J | | | | ALL |
| 210R | 20 | | VG | C | 0-0 | 49-14-11 | D04082J | | 10 | | | | D04030J | | | | ALL |
| 210Z | | | | C | 0-0 | 49-14-11 | D04082J | | | | FA | | D04030J | | | | ALL |
| 211B | 20 | | VG | T | 40-0 | 49-14-11 | D04082J | | 40 | | | | D04024J | | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0240
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0242 | 286T0242 | | | E6 TO APU FWD-A2-APU CONTROL (continued) | | | | | | | | | | | |
| 211R | 20 | VG | T | | 0-0 | 49-14-11 | D04082J | 41 | | | | D04024J | 11 | | ALL |
| 211Z | | | T | | 0-0 | 49-14-11 | D04082J | | | FA | | D04024J | DED | | ALL |
| 213B | 20 | VG | W | | 40-1 | 49-14-11 | D04082J | 52 | | | | D04030J | 5 | | ALL |
| 213R | 20 | VG | W | | 0-0 | 49-14-11 | D04082J | 53 | | | | D04030J | 6 | | ALL |
| 213Z | | | W | | 0-0 | 49-14-11 | D04082J | | | FA | | D04030J | | FD | ALL |
| 214B | 20 | VG | V | | 40-1 | 49-14-11 | D04082J | 54 | | | | D04030J | 14 | | ALL |
| 214R | 20 | VG | V | | 0-0 | 49-14-11 | D04082J | 55 | | | | D04030J | 15 | | ALL |
| 214Z | | | V | | 0-0 | 49-14-11 | D04082J | | | FA | | D04030J | | FD | ALL |
| 301B | 18 | UC | M | | 40-1 | 24-21-41 | D04040J | 2 | DK | | | D04018J | 2 | | ALL |
| 301R | 18 | UC | M | | 0-0 | 24-21-41 | D04040J | 3 | DK | | | D04018J | 3 | | ALL |
| 301Y | 18 | UC | M | | 0-0 | 24-21-41 | D04040J | 4 | DK | | | D04018J | 4 | | ALL |
| 302B | 20 | UC | R | | 40-4 | 49-94-14 | D06424J | 2 | | | | D04024J | 22 | | ALL |
| 302R | 20 | UC | R | | 0-0 | 49-94-14 | D06424J | 1 | | | | D04024J | 21 | | ALL |
| 302Y | 20 | UC | R | | 0-0 | 49-94-14 | D06424J | 3 | | | | D04024J | 23 | | ALL |
| 404B | 20 | UD | P | | 40-1 | 24-21-41 | D04040J | 8 | | | | D04018J | 8 | | ALL |
| 404G | 20 | UD | P | | 0-0 | 24-21-41 | D04040J | 9 | | | | D04018J | 9 | | ALL |
| 404R | 20 | UD | P | | 0-0 | 24-21-41 | D04040J | 10 | | | | D04018J | 10 | | ALL |
| 404Y | 20 | UD | P | | 0-0 | 24-21-41 | D04040J | 11 | | | | D04018J | 11 | | ALL |
| 452G | 20 | DU | J | | 40-1 | 49-14-11 | D04082J | 27 | 4E | | | D04030J | 9 | 4B | ALL |
| 452W | 20 | DU | J | | 0-0 | 49-14-11 | D04082J | 26 | 4I | | | D04030J | 23 | 4D | ALL |
| 452Z | | | J | | 0-0 | 49-14-11 | D04082J | | | FB | | D04030J | 40 | | ALL |
| 453G | 20 | DU | K | | 40-1 | 49-14-11 | D04082J | 30 | 4E | | | D04030J | 11 | 4B | ALL |
| 453W | 20 | DU | K | | 0-0 | 49-14-11 | D04082J | 29 | 4I | | | D04030J | 25 | 4D | ALL |
| 453Z | | | K | | 0-0 | 49-14-11 | D04082J | | | FB | | D04030J | 42 | | ALL |
| 454G | 20 | DU | L | | 40-1 | 49-14-11 | D04082J | 33 | 4E | | | D04030J | 10 | 4B | ALL |
| 454W | 20 | DU | L | | 0-0 | 49-14-11 | D04082J | 32 | 4I | | | D04030J | 24 | 4D | ALL |
| 454Z | | | L | | 0-0 | 49-14-11 | D04082J | | | FB | | D04030J | 41 | | ALL |
| 801 | 20 | UA | | | 40-1 | SPARE | D04040J | 17 | | | | D04024J | CAP | Y | 150-199 |
| 801 | 20 | UA | | | 40-1 | SPARE | D04040J | 17 | | | | D04024J | 30 | | 275-299 |
| 802 | 20 | UA | | | 40-1 | SPARE | D04040J | 18 | | | | D04018J | 14 | | ALL |
| 803 | 20 | UA | | | 40-2 | SPARE | D04040J | 19 | | | | D04030J | 20 | | ALL |
| A-A | | | | | 0-0 | 33-31-31 | L00178 | | BLK | | | SP00612 | 9 | | ALL |
| A-B | | | | | 0-0 | 33-31-31 | L00178 | | WHT | | | GD01668 | A.. | N | ALL |
| A-C | | | | | 0-0 | 33-31-31 | L00179 | | BLK | | | SP00614 | 9 | | ALL |
| A-D | | | | | 0-0 | 33-31-31 | L00179 | | WHT | | | GD01670 | A.. | N | ALL |
| A-E | | | | | 0-0 | 49-15-11 | S00506 | | = A | | | GD01634 | D.. | N | ALL |
| A-F | | | | | 0-0 | 49-15-11 | S00506 | | = B | | | SP01510 | 9 | | ALL |
| FRA | | | | | 0-0 | 49-14-11 | D04082J | | | FA | | D04082J | 25 | | ALL |
| FRB | | | | | 0-0 | 49-14-11 | D04082J | | | FB | | D04082J | 28 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0240

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|---------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0242 | 286T0242 | | | E6 TO APU FWD-A2-APU CONTROL (continued) | | | | | | | | | | | |
| FRC | | | | | 1-0 | 49-14-11 | D04030J | | | | FC | D04030J | 33 | | ALL |
| W0243 | 286T0243 | | | HF-L COAX,THRU PRESS. SEAL TO COUPLER DISC | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-11-11 | D04003J | = C1 | | | D04839J | = C1 | | | ALL |
| 01CX | | BS | | A | 36-0 | 23-11-11 | D04003J | = A1 | | | D04839J | = A1 | | | 050-099, 150-154, 162-164, 275-276 |
| 01CX | | 65 | | A | 35-3 | 23-11-11 | D04003J | = A1 | | | D04839J | = A1 | | | 155-157, 165-199, 277-299 |
| W0244 | 286T0244 | | | APU COMPARTMENT-A1-APU STARTER POWER FEEDER | | | | | | | | | | | |
| 001 | *1 | | | HA | 5-6 | 49-41-11 | D04138P | | A | | M00893 | + | R | * | ALL |
| 002 | *1 | | | HA | 5-6 | 49-41-11 | D04138P | | B | | M00893 | + | R | * | ALL |
| 003 | *1 | | | HA | 5-0 | 49-41-11 | D04138P | | C | | M00893 | - | Q | | ALL |
| 004 | *1 | | | HA | 5-0 | 49-41-11 | D04138P | | D | | M00893 | - | Q | | ALL |
| W0245 | 286T0245 | | | HF-R COAX,SHELF TO TAIL DISC | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-11-21 | D04005J | = C1 | | | D04007J | = C1 | | | ALL |
| 01CX | | BS | | A | 124-0 | 23-11-21 | D04005J | = A1 | | | D04007J | = A1 | | | 050-099 |
| 01CX | | BS | | A | 145-0 | 23-11-21 | D04005J | = A1 | | | D04007J | = A1 | | | 150-199, 275-299 |
| W0246 | 286T0246 | | | E6-1 TO APU FIREWALL-A1-APU STARTER POWER FEEDER | | | | | | | | | | | |
| 001 | *1 | | | HA | 3-1 | 49-41-11 | D04138J | | A | | SM00001 | | G* | | ALL |
| 002 | *1 | | | HA | 3-1 | 49-41-11 | D04138J | | B | | SM00002 | | G* | | ALL |
| 003 | *1 | | | HA | 3-1 | 49-41-11 | D04138J | | C | | GD01300 | D.. | H8 | | ALL |
| 004 | *1 | | | HA | 3-1 | 49-41-11 | D04138J | | D | | GD01300 | D.. | H8 | | ALL |
| 005 | *3 | | | QY | 37-6 | 49-41-11 | SM00003 | | G* | | SM00001 | | G* | | ALL |
| 006 | *3 | | | QY | 37-6 | 49-41-11 | SM00004 | | G* | | SM00002 | | G* | | ALL |
| 007 | *1 | | | HA | 1-11 | 49-41-11 | K00117 | | A1 R | | SM00003 | | G* | | ALL |
| 008 | *1 | | | HA | 1-11 | 49-41-11 | K00117 | | A1 R | | SM00004 | | G* | | ALL |
| 009 | *1 | | | HA | 3-0 | 24-32-41 | T00189 | | - R | | GD03072 | D.. | R | | 275-299 |
| 010 | *1 | | | HA | 4-0 | 24-32-41 | T00189 | | + R | | K00117 | A1 | R | | 275-299 |
| W0247 | 286T0247 | | | HF-R COAX,THRU PRESS. SEAL TO COUPLER DISC | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-11-21 | D04007P | = C1 | | | D04841J | = C1 | | | ALL |
| 01CX | | BS | | A | 36-0 | 23-11-21 | D04007P | = A1 | | | D04841J | = A1 | | | 050-099, 150-154, 162-164, 275-276 |
| 01CX | | 65 | | A | 35-2 | 23-11-21 | D04007P | = A1 | | | D04841J | = A1 | | | 155-157, 165-199, 277-299 |

WIRE LIST

D280T132

91-21-11
Section W0240
Page 6
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0248 | 286T0248 | | | P34 TO E6-A2-APU CONTROL | | | | | | | | | | | | | | |
| 001 | 24 | | PK | 112-0 | 24-51-71 | D04028P | | 25 | | | | | D04046J | | 1 | | | 050-099 |
| 001 | 24 | | PK | 133-0 | 24-51-71 | D04028P | | 25 | | | | | D04046J | | 1 | | | 150-199, 275-299 |
| 002 | 24 | | PK | 112-0 | 24-51-71 | D04028P | | 26 | | | | | D04046J | | 2 | | | 050-099 |
| 002 | 24 | | PK | 133-0 | 24-51-71 | D04028P | | 26 | | | | | D04046J | | 2 | | | 150-199, 275-299 |
| 005 | 22 | | PA | 11-0 | 49-61-11 | D04028P | | 5 | | | | | D04056P | | 14 | | | ALL |
| 006 | 22 | | PA | 112-0 | 49-61-11 | D04028P | | 6 | | | | | D04046J | | 6 | | | 050-099 |
| 006 | 22 | | PA | 133-0 | 49-61-11 | D04028P | | 6 | | | | | D04046J | | 6 | | | 150-199, 275-299 |
| 007 | 22 | | PA | 112-0 | 49-61-11 | D04028P | | 7 | | | | | D04046J | | 7 | | | 050-099 |
| 007 | 22 | | PA | 133-0 | 49-61-11 | D04028P | | 7 | | | | | D04046J | | 7 | | | 150-199, 275-299 |
| 010 | 24 | | PK | 25-0 | 24-27-11 | D04028P | | 12 | | | | | D04038P | | 1 | | | 050-099 |
| 010 | 24 | | PK | 24-8 | 24-27-11 | D04028P | | 12 | | | | | D04038P | | 1 | | | 150-199, 275-299 |
| 011 | 24 | | PK | 25-0 | 24-41-12 | D04028P | | 13 | | | | | D04038P | | 2 | | | 050-099 |
| 011 | 24 | | PK | 24-8 | 24-41-12 | D04028P | | 13 | | | | | D04038P | | 2 | | | 150-199, 275-299 |
| 012 | 22 | | PA | 11-0 | 49-61-11 | D04028P | | 14 | | | | | D04056P | | 1 | | | ALL |
| 013 | 22 | | PA | 11-0 | 49-61-11 | D04028P | | 15 | | | | | D04056P | | 2 | | | ALL |
| 014 | 24 | | PK | 14-0 | 24-22-41 | D04072J | | 12 | | | | | D04056P | | 3 | | | ALL |
| 015 | 24 | | PK | 13-0 | 24-27-11 | D04072J | | 17 | | | | | D04038P | | 7 | | | 050-099 |
| 015 | 24 | | PK | 12-9 | 24-27-11 | D04072J | | 17 | | | | | D04038P | | 7 | | | 150-199, 275-299 |
| 016 | 24 | | PK | 13-0 | 24-27-21 | D04072J | | 18 | | | | | D04038P | | 8 | | | 050-099 |
| 016 | 24 | | PK | 12-9 | 24-27-21 | D04072J | | 18 | | | | | D04038P | | 8 | | | 150-199, 275-299 |
| 017 | 24 | | PK | 22-0 | 24-41-11 | D04072J | | 19 | | | | | D04028P | | 31 | | | 050-099 |
| 017 | 24 | | PK | 23-0 | 24-41-11 | D04072J | | 19 | | | | | D04028P | | 31 | | | 150-199, 275-299 |
| 018 | 24 | | PK | 22-0 | 24-41-11 | D04072J | | 20 | | | | | D04028P | | 33 | | | 050-099 |
| 018 | 24 | | PK | 23-0 | 24-41-11 | D04072J | | 20 | | | | | D04028P | | 33 | | | 150-199, 275-299 |
| 019 | 24 | | PK | 22-0 | 24-41-12 | D04072J | | 21 | | | | | L00082 | | 1 | C | * | 050-099 |
| 019 | 24 | | PK | 23-0 | 24-41-12 | D04072J | | 21 | | | | | L00082 | | 1 | C | * | 150-199, 275-299 |
| 020 | 24 | | PK | 100-0 | 24-22-41 | D04072J | | 22 | | | | | D04046J | | 12 | | | 050-099 |
| 020 | 24 | | PK | 122-0 | 24-22-41 | D04072J | | 22 | | | | | D04046J | | 12 | | | 150-199, 275-299 |
| 021 | 18 | | PA | 113-0 | 33-31-31 | D04044J | | 11 | | | | | D04028P | | 34 | DL | | 050-099 |
| 021 | 18 | | PA | 133-0 | 33-31-31 | D04044J | | 11 | | | | | D04028P | | 34 | DL | | 150-199, 275-299 |
| 022 | 22 | | PA | 103-0 | 49-61-11 | D04046J | | 13 | | | | | D04056P | | 4 | | | 050-099 |
| 022 | 22 | | PA | 125-0 | 49-61-11 | D04046J | | 13 | | | | | D04056P | | 4 | | | 150-199, 275-299 |
| 023 | 22 | | PA | 103-0 | 49-61-11 | D04046J | | 14 | | | | | D04056P | | 5 | | | 050-099 |
| 023 | 22 | | PA | 125-0 | 49-61-11 | D04046J | | 14 | | | | | D04056P | | 5 | | | 150-199, 275-299 |
| 026 | 24 | | PK | 24-0 | 24-41-12 | L00083 | | 2 | | | C | | D04038P | | 9 | | | 050-099 |
| 026 | 24 | | PK | 24-2 | 24-41-12 | L00083 | | 2 | | | C | | D04038P | | 9 | | | 150-199, 275-299 |
| 027 | 24 | | PK | 103-0 | 29-11-32 | D04046J | | 20 | | | | | D04056P | | 15 | | | 050-099 |
| 027 | 24 | | PK | 125-0 | 29-11-32 | D04046J | | 20 | | | | | D04056P | | 15 | | | 150-199, 275-278 |
| 027 | 24 | | PK | 128-0 | 29-11-32 | D04046J | | 20 | | | | | D04056P | | 15 | | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0240

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0248 | 286T0248 | | | P34 TO E6-A2-APU CONTROL (continued) | | | | | | | | | | | | | |
| 031 | 22 | PA | | 11-0 | 49-61-11 | D04028P | | 24 | | | | | D04056P | 10 | | | ALL |
| 032 | 22 | PA | | 103-0 | 49-61-11 | D04046J | | 5 | | | | | D04056P | 12 | | | 050-099 |
| 032 | 22 | PA | | 125-0 | 49-61-11 | D04046J | | 5 | | | | | D04056P | 12 | | | 150-199, 275-299 |
| 033 | 22 | PA | | 103-0 | 49-61-11 | D04046J | | 8 | | | | | D04056P | 13 | | | 050-099 |
| 033 | 22 | PA | | 125-0 | 49-61-11 | D04046J | | 8 | | | | | D04056P | 13 | | | 150-199, 275-299 |
| 034 | 24 | PK | | 103-0 | SPARE | D04046J | | 19 | | | | | D04056P | 17 | | | 050-099 |
| 034 | 24 | PK | | 125-0 | SPARE | D04046J | | 19 | | | | | D04056P | 17 | | | 150-199, 275-278 |
| 034 | 24 | PK | | 125-0 | SPARE | D04046J | | 19 | | | | | D04056P | CAP | Y | | 280-299 |
| 035 | 24 | PK | | 25-0 | 24-22-12 | D04028P | | 27 | | | | | D04038P | 10 | | | 050-099 |
| 035 | 24 | PK | | 24-8 | 24-22-12 | D04028P | | 27 | | | | | D04038P | 10 | | | 150-199, 275-299 |
| 036 | 20 | PA | | 25-0 | 24-22-12 | D04028P | | 28 | | | | | D04038P | 11 | | | 050-099 |
| 036 | 20 | PA | | 24-8 | 24-22-12 | D04028P | | 28 | | | | | D04038P | 11 | | | 150-199, 275-299 |
| 037 | 24 | PK | | 10-0 | 24-41-11 | D04028P | | 30 | | | | | D00372 | E | E | | 050-099 |
| 037 | 24 | PK | | 11-0 | 24-41-11 | D04028P | | 30 | | | | | D00372 | E | E | | 150-199, 275-299 |
| 038 | 24 | PK | | 10-0 | 24-41-11 | D04028P | | 32 | | | | | D00372 | F | E | | 050-099 |
| 038 | 24 | PK | | 11-0 | 24-41-11 | D04028P | | 32 | | | | | D00372 | F | E | | 150-199, 275-299 |
| 039 | 20 | PQ | A | 22-0 | 24-22-12 | D04028P | | 29 | | | | | D04072J | 23 | | | 050-099 |
| 039 | 20 | PQ | A | 23-0 | 24-22-12 | D04028P | | 29 | | | | | D04072J | 23 | | | 150-199, 275-299 |
| 039Z | | | A | 0-0 | 24-22-12 | D04028P | | DED | | | | | D04072J | DED | | | ALL |
| 040 | 24 | PK | | 13-0 | 24-22-12 | D04038P | | 12 | | | | | D04072J | 24 | | | 050-099 |
| 040 | 24 | PK | | 12-9 | 24-22-12 | D04038P | | 12 | | | | | D04072J | 24 | | | 150-199, 275-299 |
| 041 | 24 | PK | | 13-0 | 24-22-12 | D04038P | | 13 | | | | | D04072J | 25 | | | 050-099 |
| 041 | 24 | PK | | 12-9 | 24-22-12 | D04038P | | 13 | | | | | D04072J | 25 | | | 150-199, 275-299 |
| 042 | 24 | PK | | 13-0 | 24-22-12 | D04038P | | 14 | | | | | D04072J | 26 | | | 050-099 |
| 042 | 24 | PK | | 12-9 | 24-22-12 | D04038P | | 14 | | | | | D04072J | 26 | | | 150-199, 275-299 |
| 043 | 24 | PK | | 13-0 | 24-51-31 | D04038P | | 15 | | | | | D04072J | 27 | | | 050-099 |
| 043 | 24 | PK | | 12-9 | 24-51-31 | D04038P | | 15 | | | | | D04072J | 27 | | | 150-199, 275-299 |
| 044 | 24 | PK | | 13-0 | 24-51-31 | D04038P | | 16 | | | | | D04072J | 28 | | | 050-099 |
| 044 | 24 | PK | | 12-9 | 24-51-31 | D04038P | | 16 | | | | | D04072J | 28 | | | 150-199, 275-299 |
| 045 | 24 | PK | | 4-0 | 24-41-12 | L00082 | | 1 | C | | * | | L00083 | 1 | C | | 050-099 |
| 045 | 24 | PK | | 3-0 | 24-41-12 | L00082 | | 1 | C | | * | | L00083 | 1 | C | | 150-199, 275-299 |
| 046 | 20 | PA | | 4-0 | 24-41-12 | L00082 | | 2 | C | | | | GD01884 | D.. | E | | ALL |
| 047 | 24 | PK | | 11-0 | 24-27-41 | D04056P | | 9 | | | | | D04028P | 4 | | | 050-099, 162-199, 275-299 |
| 048 | 22 | PA | | 103-0 | 49-61-11 | D04046J | | 25 | | | | | D04056P | 19 | | | 050-099 |
| 048 | 22 | PA | | 125-0 | 49-61-11 | D04056P | | 19 | | | | | D04046J | 25 | | | 162-199, 275-299 |
| 050 | 20 | PA | | 100-0 | SPARE | D04046J | | 21 | | | | | D04072J | 29 | | | 050-099 |
| 050 | 20 | PA | | 123-0 | SPARE | D04046J | | 21 | | | | | D04072J | 29 | | | 150-199, 275-299 |
| 051 | 20 | PA | | 103-0 | SPARE | D04046J | | 22 | | | | | D04056P | 22 | | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0240
Page 8
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0248 | 286T0248 | | | P34 TO E6-A2-APU CONTROL (continued) | | | | | | | | | | | | | |
| 051 | 20 | PA | | 125-0 | SPARE | D04046J | 22 | | | | | | D04056P | 22 | | | 150-199, 275-278 |
| 051 | 20 | PA | | 128-0 | SPARE | D04046J | 22 | | | | | | D04056P | 22 | | | 280-299 |
| 052 | 20 | PA | | 14-0 | SPARE | D04072J | 31 | | | | | | D04056P | 24 | | | ALL |
| 054 | 20 | PA | | 133-0 | 24-32-41 | D04028P | 9 | | | | | | D04046J | 9 | | | 275-299 |
| 057 | 24 | PK | | 112-0 | 49-71-11 | D04028P | 10 | | | | | | D04046J | 10 | | | 050-099 |
| 057 | 24 | PK | | 133-0 | 49-71-11 | D04028P | 10 | | | | | | D04046J | 10 | | | 150-199, 275-299 |
| 059 | 24 | PK | | 133-0 | 24-27-41 | D04028P | 52 | | | | | | D04044J | 12 | | | 150-157 |
| 060 | 24 | PK | | 11-0 | 28-25-21 | D04028P | 11 | | | | | | D04056P | 11 | | | ALL |
| 061 | 24 | PK | | 13-0 | 24-51-71 | D04038P | 18 | | | | | | D04072J | 33 | | | 050-099 |
| 061 | 24 | PK | | 12-9 | 24-51-71 | D04038P | 18 | | | | | | D04072J | 33 | | | 150-199, 275-299 |
| 062 | 24 | PK | | 13-0 | 24-51-71 | D04038P | 17 | | | | | | D04072J | 32 | | | 050-099 |
| 062 | 24 | PK | | 12-9 | 24-51-71 | D04038P | 17 | | | | | | D04072J | 32 | | | 150-199, 275-299 |
| 063 | 24 | PK | | 112-0 | 49-73-11 | D04028P | 43 | | | | | | D04046J | 26 | | | 050-099 |
| 063 | 24 | PK | | 133-0 | 49-73-11 | D04028P | 43 | | | | | | D04046J | 26 | | | 150-199, 275-299 |
| 065 | 20 | PA | | 100-0 | SPARE | D04046J | 24 | | | | | | D04072J | 30 | | | 050-099 |
| 065 | 20 | PA | | 122-0 | SPARE | D04046J | 24 | | | | | | D04072J | 30 | | | 150-199, 275-299 |
| 066 | 24 | PK | | 112-0 | 24-34-11 | D04046J | 23 | | | | | | D04028P | 42 | | | 050-099 |
| 066 | 24 | PK | | 133-0 | 24-34-11 | D04046J | 23 | | | | | | D04028P | 42 | | | 150-199, 275-299 |
| 070 | 24 | PK | | 112-0 | 38-15-11 | D04028P | 8 | | | | | | D04046J | 18 | | | 050-099 |
| 070 | 24 | PK | | 133-0 | 38-15-11 | D04028P | 8 | | | | | | D04046J | 18 | | | 150-199, 275-299 |
| 075 | 18 | PA | | 16-11 | 25-31-12 | D04056P | 16 | DK | | | | | D04038P | 20 | DL | | 150-154 |
| 075 | 18 | PA | | 16-11 | SPARE | D04056P | 16 | DK | | | | | D04038P | 20 | DL | | 155-199 |
| 075 | 18 | PA | | 16-11 | SPARE | D04056P | 17 | DK | | | | | D04038P | 20 | DL | | 280-299 |
| 077 | 18 | PA | | 17-0 | 25-31-12 | D04056P | 18 | DK | | | | | D04038P | 22 | DL | | 050-099 |
| 077 | 18 | PA | | 16-11 | 25-31-12 | D04056P | 18 | DK | | | | | D04038P | 22 | DL | | 150-154 |
| 077 | 20 | PA | | 16-11 | 25-31-11 | D04056P | 23 | | | | | | D04038P | 22 | | | 155-157, 165-199, 277-278 |
| 077 | 18 | PA | | 16-11 | 25-31-11 | D04056P | 23 | DK | | | | | D04038P | 22 | DL | | 162-164, 280-299 |
| 079 | 20 | PA | | 17-0 | 25-31-11 | D04056P | 23 | | | | | | D04038P | 21 | | | 050-099 |
| 110 | 16 | PA | | 25-0 | 30-71-25 | D04028P | 40 | FL | | | | | D04038P | 19 | FL | | 050-099 |
| 110 | 16 | PA | | 24-8 | 30-71-25 | D04028P | 40 | FL | | | | | D04038P | 19 | FL | | 150-199 |
| 202B | 20 | PR | D | 102-0 | 24-21-41 | D04072J | 9 | | | | | | D04044J | 1 | | | 050-099 |
| 202B | 20 | PR | D | 122-0 | 24-21-41 | D04072J | 9 | | | | | | D04044J | 1 | | | 150-199, 275-299 |
| 202R | 20 | PR | D | 0-0 | 24-21-41 | D04072J | 10 | | | | | | D04044J | 2 | | | ALL |
| 202Z | | | D | 0-0 | 24-21-41 | D04072J | 11 | | | | | | D04044J | 3 | | | ALL |
| 203B | 20 | PB | J | 103-0 | 21-61-51 | D04046J | 15 | | | | | | D04056P | 6 | | | 050-099 |
| 203B | 20 | PB | J | 125-0 | 21-61-51 | D04046J | 15 | | | | | | D04056P | 6 | | | 150-199, 275-299 |
| 203R | 20 | PB | J | 0-0 | 21-61-51 | D04046J | 16 | | | | | | D04056P | 7 | | | ALL |
| 207B | 24 | PL | N | 112-0 | 24-34-11 | D04028P | 53 | | | | | | D04046J | 28 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0240

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|---|-------|-------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0248 | 286T0248 | P34 TO E6-A2-APU CONTROL (continued) | | | | | | | | | | | | | |
| 207B | 24 | PL | N | 133-0 | 24-34-11 | D04028P | | 53 | | D04046J | | 28 | | 150-199, 275-299 | |
| 207R | 24 | PL | N | 0-0 | 24-34-11 | D04028P | | 54 | | D04046J | | 29 | | ALL | |
| 301B | 18 | PC | G | 101-0 | 24-21-41 | D04044J | | 4 | | D04074J | | 1 | | 050-099 | |
| 301B | 18 | PC | G | 122-0 | 24-21-41 | D04044J | | 4 | | D04074J | | 1 | | 150-199, 275-299 | |
| 301R | 18 | PC | G | 0-0 | 24-21-41 | D04044J | | 5 | | D04074J | | 2 | | ALL | |
| 301Y | 18 | PC | G | 0-0 | 24-21-41 | D04044J | | 6 | | D04074J | | 3 | | ALL | |
| 401B | 24 | PN | B | 22-0 | 24-23-12 | D04028P | | 16 | | D04072J | | 1 | | 050-099 | |
| 401B | 24 | PN | B | 23-0 | 24-23-12 | D04028P | | 16 | | D04072J | | 1 | | 150-199, 275-299 | |
| 401G | 24 | PN | B | 0-0 | 24-23-12 | D04028P | | 17 | | D04072J | | 2 | | ALL | |
| 401R | 24 | PN | B | 0-0 | 24-23-12 | D04028P | | 18 | | D04072J | | 3 | | ALL | |
| 401Y | 24 | PN | B | 0-0 | 24-23-12 | D04028P | | 19 | | D04072J | | 4 | | ALL | |
| 402B | 24 | PN | C | 22-0 | 24-23-12 | D04028P | | 20 | | D04072J | | 5 | | 050-099 | |
| 402B | 24 | PN | C | 23-0 | 24-23-12 | D04028P | | 20 | | D04072J | | 5 | | 150-199, 275-299 | |
| 402G | 24 | PN | C | 0-0 | 24-23-12 | D04028P | | 21 | | D04072J | | 6 | | ALL | |
| 402R | 24 | PN | C | 0-0 | 24-23-12 | D04028P | | 22 | | D04072J | | 7 | | ALL | |
| 402Y | 24 | PN | C | 0-0 | 24-23-12 | D04028P | | 23 | | D04072J | | 8 | | ALL | |
| 403B | 24 | PN | E | 13-0 | 24-23-12 | D04072J | | 13 | | D04038P | | 3 | | 050-099 | |
| 403B | 24 | PN | E | 12-9 | 24-23-12 | D04072J | | 13 | | D04038P | | 3 | | 150-199, 275-299 | |
| 403G | 24 | PN | E | 0-0 | 24-23-12 | D04072J | | 14 | | D04038P | | 4 | | ALL | |
| 403R | 24 | PN | E | 0-0 | 24-23-12 | D04072J | | 15 | | D04038P | | 5 | | ALL | |
| 403Y | 24 | PN | E | 0-0 | 24-23-12 | D04072J | | 16 | | D04038P | | 6 | | ALL | |
| 404B | 24 | PN | H | 101-0 | 24-21-41 | D04044J | | 7 | | D04074J | | 4 | | 050-099 | |
| 404B | 24 | PN | H | 122-0 | 24-21-41 | D04044J | | 7 | | D04074J | | 4 | | 150-199, 275-299 | |
| 404G | 24 | PN | H | 0-0 | 24-21-41 | D04044J | | 8 | | D04074J | | 5 | | ALL | |
| 404R | 24 | PN | H | 0-0 | 24-21-41 | D04044J | | 9 | | D04074J | | 6 | | ALL | |
| 404Y | 24 | PN | H | 0-0 | 24-21-41 | D04044J | | 10 | | D04074J | | 7 | | ALL | |
| W0249 | 286T0249 | VHF-L COAX,SHELF TO ANT. DISC | | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-12-11 | D04009J | | = C1 | | D04011J | | = C1 | | ALL | |
| 01CX | | | BS A | 48-8 | 23-12-11 | D04009J | | = A1 | | D04011J | | = A1 | | 050-099 | |
| 01CX | | | BS A | 51-4 | 23-12-11 | D04009J | | = A1 | | D04011J | | = A1 | | 150-199, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W0240
Page 10 End
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|------|-------------|---|-------|------|------|---------|-------|------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0250 | 286T0250 | | | | | | | | | | | | | | | |
| | | | | | | APU COMPARTMENT-S2-FIRE DET LOOP B | | | | | | | | | | |
| 201B | 18 | HQ | A | 4-4 | 23-41-11 | D04022P | | 5 | | SM00002 | | 8 | | ALL | | |
| 201R | 18 | HQ | A | 0-0 | 23-41-11 | D04022P | | 6 | | SM00001 | | 8 | | ALL | | |
| 201Z | | | A | 0-0 | 23-41-11 | D04022P | | 7 | | SM00003 | | 8 | | ALL | | |
| 452R | 16 | 9P | | 14-9 | 26-15-11 | D04022P | | 1 | | D00508 | =S | | | ALL | | |
| 453R | 16 | 9P | | 17-8 | 26-15-11 | D00514 | | =P | | D00516 | =P | | | ALL | | |
| 455R | 16 | 9P | | 6-2 | 26-15-11 | D04022P | | 3 | | D00506 | =S | | | ALL | | |
| A-A | | | B | 0-0 | 23-41-11 | D08505 | RED | | | SM00001 | | 8 | | ALL | | |
| A-B | | | B | 0-0 | 23-41-11 | D08505 | BLU | | | SM00002 | | 8 | | ALL | | |
| A-C | | | B | 0-0 | 23-41-11 | D08505 | BLK | | | SM00003 | | 8 | | ALL | | |
| W0251 | 286T0251 | | | | | | | | | | | | | | | |
| | | | | | | VHF-L COAX,ANT. | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-12-11 | D04011P | | =C1 | | D00005 | =C1 | | | ALL | | |
| 01CX | | | BS A | 1-6 | 23-12-11 | D04011P | | =A1 | | D00005 | =A1 | | | ALL | | |
| W0252 | 286T0252 | | | | | | | | | | | | | | | |
| | | | | | | P6 TO E3-2-L1-LEFT TRU POWER | | | | | | | | | | |
| 001 | 14 | PA | | 21-0 | 24-32-11 | D00358 | | 8 | | D04116P | | 1 | | ALL | | |
| 002 | 14 | PA | | 21-0 | 24-32-11 | D00358 | | 7 | | D04116P | | 2 | | ALL | | |
| 003 | 14 | PA | | 21-0 | 24-32-11 | D00358 | | 6 | | D04116P | | 3 | | ALL | | |
| 006 | 14 | PA | | 6-0 | 24-32-11 | D00358 | | 5 | | GD02772 | S.. | E | | ALL | | |
| 201B | 18 | PB | A | 21-0 | 24-34-11 | D04118P | | 3 | DK | D00358 | | 3 | | ALL | | |
| 201R | 18 | PB | A | 0-0 | 24-34-11 | D04118P | | 4 | DK | D00358 | | 4 | | ALL | | |
| W0253 | 286T0253 | | | | | | | | | | | | | | | |
| | | | | | | VHF-R COAX,SHELF TO ANT. | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-12-21 | D04013J | | =C1 | | D00007 | =C1 | | | ALL | | |
| 01CX | | | 65 A | 24-0 | 23-12-21 | D04013J | | =A1 | | D00007 | =A1 | | | ALL | | |
| W0254 | 286T0254 | | | | | | | | | | | | | | | |
| | | | | | | P6 TO E3-2-R1-RIGHT TRU POWER | | | | | | | | | | |
| 001 | 14 | PA | | 18-0 | 24-32-11 | D00360 | | 8 | | D04120P | | 1 | | ALL | | |
| 002 | 14 | PA | | 18-0 | 24-32-11 | D00360 | | 7 | | D04120P | | 2 | | ALL | | |
| 003 | 14 | PA | | 18-0 | 24-32-11 | D00360 | | 6 | | D04120P | | 3 | | ALL | | |
| 006 | 14 | PA | | 4-0 | 24-32-11 | D00360 | | 5 | | GD02776 | S.. | E | | ALL | | |
| 201B | 18 | PB | A | 19-0 | 24-34-11 | D04122P | | 3 | DK | D00360 | | 3 | | ALL | | |
| 201R | 18 | PB | A | 0-0 | 24-34-11 | D04122P | | 4 | DK | D00360 | | 4 | | ALL | | |
| W0256 | 286T0256 | | | | | | | | | | | | | | | |
| | | | | | | P6 TO E3-S1-MAIN BAT & STATIC INVERTER | | | | | | | | | | |
| 001 | 24 | PK | | 24-0 | 24-31-11 | D00320 | | 8 | | D04126P | | 1 | | ALL | | |
| 002 | 20 | PA | | 6-0 | 24-31-11 | D00320 | | 2 | | GD01882 | S.. | E | | ALL | | |
| 003 | 24 | PK | | 25-0 | 24-34-11 | D10182 | | 11 | | D04126P | | 7 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0250

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|-------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0256 | 286T0256 | | | P6 TO E3-S1-MAIN BAT & STATIC INVERTER (continued) | | | | | | | | | | | |
| 004 | 24 | | PK | | 25-0 | 24-34-11 | D10182 | | 7 | | D04126P | | 8 | | ALL |
| 005 | 24 | | PK | | 10-0 | 24-31-11 | D00320 | | 11 | | D00364 | | 11 | | ALL |
| 006 | 24 | | PK | | 10-0 | 24-31-11 | D00320 | | 12 | | D00364 | | 12 | | ALL |
| 007 | 24 | | PK | | 11-0 | 24-31-11 | D00320 | | 1 | | D00364 | | 1 | | ALL |
| 008 | 24 | | PK | | 11-0 | 24-31-11 | D00320 | | 3 | | D00364 | | 3 | | ALL |
| 010 | 14 | | PQ | C | 25-0 | 24-33-11 | D00362 | | 1 | | D04124P | | 1 | | ALL |
| 010Z | | | | C | 0-0 | 24-33-11 | D00362 | DED | | | D04124P | DED | | | ALL |
| 011 | 24 | | PK | | 24-0 | 24-34-11 | D00320 | | 9 | | D04126P | | 9 | | ALL |
| 012 | 14 | | PA | | 4-0 | 24-33-11 | D00362 | | 3 | | GD01880 | A.. | E | | ALL |
| 013 | 14 | | PA | | 4-0 | 24-33-11 | D00362 | | 2 | | GD01882 | S.. | E | | ALL |
| 014 | 24 | | PK | | 24-0 | 24-31-11 | D00364 | | 8 | | D04126P | | 3 | | ALL |
| 015 | 20 | | PA | | 11-0 | 24-31-11 | D00364 | | 9 | | GD01884 | D.. | E | | ALL |
| 019 | 24 | | PK | | 25-0 | 24-34-11 | D10182 | | 4 | | D04126P | | 10 | | ALL |
| 020 | 20 | | PA | | 3-0 | 24-34-11 | D10182 | | 9 | | GD04588 | D.. | E | | ALL |
| 021 | 20 | | PA | | 3-0 | 24-34-11 | D10182 | | 2 | | GD04590 | S.. | E | | ALL |
| 022 | 22 | | PA | | 1-0 | 24-31-11 | D00320 | | 5 | | D00320 | | 6 | | ALL |
| 201B | 24 | | PL | B | 25-0 | 24-34-11 | D04126P | | 11 | | M00224 | C | D | | ALL |
| 201R | 24 | | PL | B | 0-0 | 24-34-11 | D04126P | | 12 | | M00224 | D | D | | ALL |
| 301B | 20 | | PS | A | 12-0 | 24-31-11 | D00320 | | 4 | | D04128P | | 1 | | ALL |
| 301R | 20 | | PS | A | 0-0 | 24-31-11 | D00320 | | 7 | | D04128P | | 2 | | ALL |
| 301Y | 20 | | PS | A | 0-0 | 24-31-11 | D00320 | | 10 | | D04128P | | 3 | | ALL |
| 301Z | | | | A | 0-0 | 24-31-11 | D00320 | DED | | | D04128P | DED | | | ALL |
| W0257 | 286T0257 | | | VHF-C COAX,SHELF TO ANT.DISC | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-12-31 | D04017J | | = C1 | | D04019J | | = C1 | | ALL |
| 01CX | | | | BS | 116-0 | 23-12-31 | D04017J | | = A1 | | D04019J | | = A1 | | 050-099 |
| 01CX | | | | BS | 124-0 | 23-12-31 | D04017J | | = A1 | | D04019J | | = A1 | | 150-199, 275-299 |
| W0258 | 286T0258 | | | P6 TO E3-S1-MAIN BAT PWR FEEDER | | | | | | | | | | | |
| 001 | *1 | | HA | | 18-0 | 24-31-11 | D00366 | | + Q | | TB5014 | | 1 Q | | ALL |
| 002 | *1 | | HA | | 3-0 | 24-31-11 | D00366 | | - Q | | M00224 | | A F | | ALL |
| 003 | *1 | | HA | | 2-0 | 24-31-11 | GD01886 | | D.. F | | M00224 | | B F | | ALL |
| W0259 | 286T0259 | | | VHF-C COAX,ANT | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-12-31 | D04019P | | = C1 | | D00009 | | = C1 | | ALL |
| 01CX | | | | BS | 7-0 | 23-12-31 | D04019P | | = A1 | | D00009 | | = A1 | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0260 | 286T0260 | | | APU COMPARTMENT-S2-FIRE DET LOOP A | | | | | | | | | | | | |
| 452R | 16 | | 9P | 14-10 | 26-15-11 | D04020P | | 2 | | | | | D00510 | =P | | ALL |
| 453R | 16 | | 9P | 17-8 | 26-15-11 | D00518 | | =S | | | | | D00520 | =S | | ALL |
| 455R | 16 | | 9P | 6-0 | 26-15-11 | D04020P | | 3 | | | | | D00512 | =P | | ALL |
| W0261 | 286T0261 | | | ILS-L COAX,ANT.TO FWD PRESS BLKHD,LOC | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-31-11 | D04043P | | =C1 | | | | | D00011 | =C1 | | ALL |
| 01CX | | | XE A | 2-0 | 34-31-11 | D04043P | | =A1 | | | | | D00011 | =A1 | | ALL |
| W0262 | 286T0262 | | | P61 TO R WBD-S2A-ENG INSTR | | | | | | | | | | | | |
| 001 | 20 | | PA | 20-8 | 76-11-11 | D04756P | | 1 | | | | | D08114P | 1 | | ALL |
| 003 | 24 | | PK | 57-2 | 80-11-21 | D04756P | | 3 | | | | | D04632J | 1 | | 050-099 |
| 003 | 24 | | PK | 66-11 | 80-11-21 | D04756P | | 3 | | | | | D04632J | 1 | | 150-199, 275-299 |
| 004 | 24 | | PK | 57-2 | 80-11-21 | D04756P | | 4 | | | | | D04632J | 2 | | 050-099 |
| 004 | 24 | | PK | 66-11 | 80-11-21 | D04756P | | 4 | | | | | D04632J | 2 | | 150-199, 275-299 |
| 005 | 18 | | PA | 57-2 | 80-11-21 | D04756P | | 5 | DL | | | | D04632J | 3 | DK | 050-099 |
| 005 | 18 | | PA | 66-11 | 80-11-21 | D04756P | | 5 | DL | | | | D04632J | 3 | DK | 150-199, 275-299 |
| 006 | 24 | | PK | 13-6 | 31-31-26 | D05822P | | 31 | | | | | D05676J | 3 | | ALL |
| 007 | 24 | | PK | 15-1 | 80-11-21 | D04756P | | 7 | | | | | D05822P | 1 | | ALL |
| 008 | 24 | | PK | 15-1 | 80-11-21 | D04756P | | 8 | | | | | D05822P | 2 | | ALL |
| 009 | 22 | | PA | 22-7 | SPARE | D08114P | | 8 | | | | | D05822P | 15 | | 150-199 |
| 010 | 22 | | PQ | 15-1 | 73-21-11 | D04756P | | 6 | | | | | D05822P | 16 | | ALL |
| 010Z | | | AJ | 0-0 | 73-21-11 | D04756P | | 2 | | | | | D05822P | 14 | | ALL |
| 011 | 18 | | PA | 15-1 | 24-11-21 | D04756P | | 11 | DL | | | | D05822P | 28 | DL | 050-099, 150-154, 275-276 |
| 011 | 18 | | PA | 15-1 | 24-11-21 | D05822P | | 28 | DL | | | | D04756P | 11 | DL | 155-199, 277-299 |
| 012 | 20 | | PA | 20-11 | 24-11-21 | D04756P | | 12 | | | | | D05676J | 2 | | ALL |
| 013 | 20 | | PA | 22-7 | 76-11-11 | D08114P | | 3 | | | | | D05822P | 5 | | ALL |
| 014 | 20 | | PA | 22-7 | 76-11-11 | D08114P | | 4 | | | | | D05822P | 6 | | ALL |
| 015 | 20 | | PA | 22-7 | 76-11-11 | D08114P | | 5 | | | | | D05822P | 21 | | ALL |
| 017 | 20 | | PA | 15-1 | 76-11-11 | D04756P | | 25 | | | | | D05822P | 29 | | ALL |
| 018 | 24 | | PK | 22-7 | 73-21-11 | D05822P | | 26 | | | | | D08114P | 21 | | ALL |
| 020 | 24 | | PK | 22-7 | 73-21-11 | D05822P | | 27 | | | | | D08114P | 6 | | ALL |
| 021 | 20 | | PA | 49-3 | 76-11-11 | D05822P | | 11 | | | | | D04632J | 9 | | 050-099 |
| 021 | 20 | | PA | 59-6 | 76-11-11 | D05822P | | 11 | | | | | D04632J | 9 | | 150-199, 275-299 |
| 022 | 20 | | PA | 49-3 | 76-11-11 | D05822P | | 12 | | | | | D04632J | 10 | | 050-099 |
| 022 | 20 | | PA | 59-6 | 76-11-11 | D05822P | | 12 | | | | | D04632J | 10 | | 150-199, 275-299 |
| 023 | 20 | | PA | 49-3 | 76-11-11 | D05822P | | 19 | | | | | D04632J | 12 | | 050-099 |
| 023 | 20 | | PA | 59-6 | 76-11-11 | D05822P | | 19 | | | | | D04632J | 12 | | 150-199 |
| 023 | 20 | | PA | 59-6 | 76-11-11 | D05822P | | 15 | | | | | D04632J | 12 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0260

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|---|-------|-------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0262 | 286T0262 | P61 TO R WBD-S2A-ENG INSTR (continued) | | | | | | | | | | | | | | | |
| 024 | 24 | | PK | 20-8 | 73-21-11 | D04756P | | 40 | | | | | D08114P | 22 | | | ALL |
| 025R | 22 | | PH | 20-8 | 26-11-21 | D08114P | | 9 | | | | | D04756P | 13 | | | ALL |
| 026 | 20 | | PA | 20-8 | 28-22-21 | D08114P | | 10 | | | | | D04756P | 14 | | | ALL |
| 030 | 18 | | PA | 15-1 | 78-34-21 | D05822P | | 4 | DL | | | | D04756P | 23 | DL | | ALL |
| 031 | 20 | | PA | 20-8 | 27-41-21 | D08114P | | 11 | | | | | D04756P | 19 | | | ALL |
| 032 | 22 | | PA | 20-11 | 33-16-22 | D05676J | | 9 | | | | | D04756P | 20 | | | ALL |
| 035 | 20 | | PA | 49-3 | SPARE | D05822P | | 25 | | | | | D04632J | 14 | | | 050-099 |
| 036 | 22 | | PA | 29-11 | 33-16-18 | D08114P | | 13 | | | | | TB0031H | 16 | 2 | | ALL |
| 037 | 22 | | PA | 29-11 | 33-16-18 | D08114P | | 12 | | | | | TB0031H | 11 | 2 | | ALL |
| 039 | 18 | | PA | 22-7 | 28-22-21 | D05822P | | 17 | DL | | | | D08114P | 14 | DK | | 050-099, 150-154, 156-162, 165-199 |
| 039 | 18 | | PA | 11-6 | 28-22-21 | SM00002 | | | S | | | | D08114P | 14 | DK | | 155, 163-164, 275-299 |
| 040 | 18 | | PA | 22-7 | 28-22-21 | D05822P | | 18 | DL | | | | D08114P | 15 | DK | | ALL |
| 041 | 20 | | PA | 15-1 | SPARE | D05822P | | 19 | | | | | D04756P | 15 | | | 275-299 |
| 048 | 22 | | PA | 22-7 | 28-22-21 | D08114P | | 17 | | | | | D05822P | 20 | | | ALL |
| 050 | 20 | | PA | 49-3 | SPARE | D05822P | | 23 | | | | | D04632J | 23 | | | 050-099 |
| 050 | 20 | | PA | 59-6 | SPARE | D05822P | | 23 | | | | | D04632J | 23 | | | 150-199, 275-299 |
| 051 | 20 | | PA | 57-2 | SPARE | D04632J | | 24 | | | | | D04756P | 30 | | | 050-099 |
| 051 | 20 | | PA | 66-11 | SPARE | D04632J | | 24 | | | | | D04756P | 30 | | | 150-199, 275-299 |
| 056 | 20 | | PA | 49-3 | SPARE | D05822P | | | CAP | Y | | | D04632J | 22 | | | 050-099 |
| 056 | 20 | | PA | 59-6 | SPARE | D05822P | | | CAP | Y | | | D04632J | 22 | | | 150-154, 275-276 |
| 062 | 20 | | PA | 49-3 | 76-11-11 | D05822P | | 22 | | | | | D04632J | 5 | | | 050-099 |
| 062 | 20 | | PA | 59-6 | 76-11-11 | D05822P | | 22 | | | | | D04632J | 5 | | | 150-199, 275-299 |
| 120 | 24 | | PK | 15-1 | 27-51-61 | D05822P | | 7 | | | | | D04756P | 17 | | | ALL |
| 121 | 22 | | PA | 13-6 | 27-51-61 | D05822P | | 8 | | | | | D05676J | 7 | | | ALL |
| 122 | 24 | | PK | 20-11 | 27-51-61 | D04756P | | 18 | | | | | D05676J | 8 | | | ALL |
| 138 | 20 | | PQ | FM | 4-6 | 28-22-21 | SM00002 | | | S | | | SP09728 | | S | | 155, 163-164, 275-278 |
| 138 | 20 | | PQ | FM | 4-6 | 28-22-21 | SP09728 | | | S | | | SM00002 | | S | | 280-299 |
| 138Z | | | FM | 0-0 | 28-22-21 | SM00002 | | | DED | | | | SP09728 | | DED | | 155, 163-164, 275-278 |
| 138Z | | | FM | 0-0 | 28-22-21 | SP09728 | | | DED | | | | SM00002 | | DED | | 280-299 |
| 139 | 18 | | PA | 6-9 | 28-22-21 | SM00002 | | | S | | | | D05822P | 17 | DL | | 155, 163-164, 280-299 |
| 139 | 18 | | PA | 6-9 | 28-22-21 | SM00002 | | | S | | | | D05822P | 17 | DK | | 275-278 |
| 173 | 18 | | PA | 13-6 | 24-11-21 | D05822P | | 10 | DL | | | | D05676J | 1 | DL | | ALL |
| 801 | 20 | | PA | 15-1 | SPARE | D05822P | | 24 | | | | | D04756P | 29 | | | ALL |
| 802 | 20 | | PA | 20-11 | SPARE | D05676J | | 12 | | | | | D04756P | 31 | | | ALL |
| W0263 | 286T0263 | ILS-L COAX,E1-3 TO FWD PRESS BLKHD,LOC | | | | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-31-11 | D04043J | | | = C1 | | | | D04045P | | = C1 | | ALL |
| 01CX | | | XE | A | 29-0 | 34-31-11 | D04043J | | = A1 | | | | D04045P | | = A1 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0260
Page 2
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0264 | 286T0264 | | | P61 TO L W/W-S2B-FLT CONT/ENG INSTR | | | | | | | | | | | | |
| 001 | 20 | | PA | 37-7 | 76-11-11 | D08026P | | 1 | | | D08118P | | 1 | | ALL | |
| 002 | 20 | | PA | 37-7 | 76-11-11 | D08026P | | 2 | | | D08118P | | 2 | | ALL | |
| 003 | 20 | | PA | 37-7 | 76-11-11 | D08118P | | 3 | | | D08026P | | 12 | | 050-099, 150-199 | |
| 003 | 20 | | PA | 37-7 | 76-11-11 | D08026P | | 12 | | | D08118P | | 3 | | 275-299 | |
| 005 | 22 | | PA | 37-7 | 32-44-11 | D08026P | | 6 | | | D08118P | | 5 | | ALL | |
| 006 | 22 | | PQ | AF | 12-7 | 28-42-12 | D08026P | | 5 | | D04042P | | 18 | | 050-099, 155-199, 276-299 | |
| 006 | 22 | | PA | 37-7 | SPARE | D08026P | | 5 | | | D08118P | | 6 | | 150-154 | |
| 006Z | | | | AF | 0-0 | 28-42-12 | D08026P | | DED | | D04042P | | DED | | 050-099, 155-199, 276-299 | |
| 007 | 24 | | PK | 37-7 | 29-11-32 | D08026P | | 7 | | | D08118P | | 8 | | ALL | |
| 008 | 18 | | PA | 21-5 | 32-44-11 | D08026P | | 8 | DK | | S00459 | | 1NC | B | ALL | |
| 009 | 18 | | PA | 21-5 | 32-44-11 | D08026P | | 9 | DK | | S00459 | | 1NO | B | ALL | |
| 010 | 20 | | PA | 48-3 | 76-11-11 | D08026P | | 10 | | | D04634J | | 1 | | 050-099 | |
| 010 | 20 | | PA | 58-8 | 76-11-11 | D08026P | | 10 | | | D04634J | | 1 | | 150-199, 275-299 | |
| 011 | 20 | | PA | 48-3 | 76-11-11 | D08026P | | 11 | | | D04634J | | 2 | | 050-099 | |
| 011 | 20 | | PA | 58-8 | 76-11-11 | D08026P | | 11 | | | D04634J | | 2 | | 150-199, 275-299 | |
| 013 | 20 | | PA | 12-7 | 30-34-11 | D04042P | | 20 | | | D08026P | | 40 | | 050-099, 150-199 | |
| 013 | 20 | | PA | 12-7 | 30-34-11 | D08026P | | 40 | | | D04042P | | 20 | | 275-299 | |
| 014 | 20 | | PA | 20-2 | 76-11-11 | D04774P | | 1 | | | D08118P | | 10 | | ALL | |
| 015 | 20 | | PA | 20-2 | SPARE | D04774P | | 2 | | | D08118P | | 11 | | 275-299 | |
| 016 | 18 | | PA | 28-6 | 32-44-11 | D04774P | | 3 | DL | | S00459 | | 1C | B | ALL | |
| 017 | 24 | | PV | AG | 12-10 | 73-21-14 | D04042P | | 5 | | D06310P | | 5 | | 050-099, 150-199 | |
| 017 | 24 | | PV | AQ | 12-10 | 73-21-14 | D04042P | | 5 | | D06310P | | 5 | | 275-299 | |
| 017Z | | | | AQ | 0-0 | 73-21-14 | D04042P | | 13 | | D06310P | | 13 | | 050-099, 150-199 | |
| 017Z | | | | AQ | 0-0 | 73-21-14 | D04042P | | 13 | | D06310P | | 13 | | 275-299 | |
| 018 | 24 | | PK | 72-0 | 80-11-11 | D04774P | | 5 | | | D04634J | | 6 | | 050-099 | |
| 018 | 24 | | PK | 81-11 | 80-11-11 | D04774P | | 5 | | | D04634J | | 6 | | 150-199, 275-299 | |
| 019 | 24 | | PK | 72-0 | 80-11-11 | D04774P | | 6 | | | D04634J | | 7 | | 050-099 | |
| 019 | 24 | | PK | 81-11 | 80-11-11 | D04774P | | 6 | | | D04634J | | 7 | | 150-199, 275-299 | |
| 020 | 18 | | PA | 72-0 | 80-11-11 | D04774P | | 7 | DL | | D04634J | | 8 | DK | 050-099 | |
| 020 | 18 | | PA | 81-11 | 80-11-11 | D04774P | | 7 | DL | | D04634J | | 8 | DK | 150-199, 275-299 | |
| 023 | 24 | | PK | 28-10 | 27-58-21 | D08026P | | 14 | | | D04774P | | 8 | | ALL | |
| 024 | 24 | | PK | 28-10 | 80-11-11 | D08026P | | 15 | | | D04774P | | 9 | | ALL | |
| 025 | 24 | | PK | 28-10 | 80-11-11 | D08026P | | 16 | | | D04774P | | 10 | | ALL | |
| 026 | 22 | | PA | 28-2 | 27-58-21 | D08026P | | 17 | | | D08028P | | 1 | | ALL | |
| 027 | 22 | | PQ | BB | 17-1 | 28-31-12 | D04774P | | 38 | | D08028P | | 16 | | 050, 155-199, 277-299 | |
| 027 | 22 | | PA | 17-1 | 28-31-12 | D04774P | | 38 | | | D08028P | | 16 | | 051-099 | |
| 027 | 22 | | PA | 28-2 | SPARE | D08026P | | 18 | | | D08028P | | 16 | | 150-154, 275-276 | |

WIRE LIST

D280T132

91-21-11

Section W0260

Page 3

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0264 | 286T0264 | | | P61 TO L W/W-S2B-FLT CONT/ENG INSTR (continued) | | | | | | | | | | | |
| 027Z | | | | BB | 0-0 | 28-31-12 | D04774P | | DED | | D08028P | | DED | | 050, 155-199, 277-299 |
| 028 | 22 | | PA | | 28-2 | SPARE | D08026P | | 19 | | D08028P | | 17 | | ALL |
| 029 | 22 | | PQ | BD | 17-1 | 73-21-11 | D04774P | | 11 | | D08028P | | 4 | | ALL |
| 029Z | | | | BD | 0-0 | 73-21-11 | D04774P | | 14 | | D08028P | | 5 | | ALL |
| 031 | 24 | | PK | | 10-7 | 29-11-32 | D08026P | | 21 | | D05646J | | 1 | | ALL |
| 033 | 20 | | PA | | 33-10 | 24-11-11 | D04774P | | 12 | | D05646J | | 3 | | ALL |
| 034 | 18 | | PA | | 29-2 | 24-11-11 | D05854P | | 6 | | D06310P | | 24 | DK | 050-099, 150-154, 275-276 |
| 034 | 18 | | PA | | 29-2 | 24-11-11 | D06310P | | 24 | DK | D05854P | | 6 | | 155-199, 277-299 |
| 035 | 20 | | PA | | 48-3 | SPARE | D08026P | | 51 | | D04634J | | 14 | | 050-099 |
| 036 | 12 | | PA | | 37-8 | 34-21-11 | D05854P | | 1 | | D04753J | | 1 | | ALL |
| 037 | 24 | | PK | | 38-1 | 24-31-11 | D04774P | | 20 | | D04042P | | 1 | | ALL |
| 038 | 24 | | PK | | 38-1 | 24-31-11 | D04774P | | 21 | | D04042P | | 2 | | ALL |
| 039R | 22 | | PH | | 20-2 | 26-11-11 | D04774P | | 18 | | D08118P | | 15 | | ALL |
| 040 | 24 | | PK | | 20-2 | 73-21-11 | D04774P | | 50 | | D08118P | | 7 | | ALL |
| 041 | 18 | | PA | | 38-1 | SPARE | D04774P | | 30 | DL | D04042P | | 7 | DK | 050-099 |
| 042 | 18 | | PA | | 38-1 | SPARE | D04774P | | 31 | DL | D04042P | | 8 | DK | 050-099 |
| 046 | 20 | | PA | | 20-2 | 28-22-21 | D04774P | | 13 | | D08118P | | 16 | | ALL |
| 047 | 24 | | PK | | 37-7 | 73-21-11 | D08118P | | 12 | | D08026P | | 43 | | 050-099, 150-199 |
| 047 | 24 | | PK | | 37-7 | 73-21-11 | D08026P | | 43 | | D08118P | | 12 | | 275-299 |
| 048 | 24 | | PK | | 37-7 | 73-21-11 | D08118P | | 4 | | D08026P | | 44 | | 050-099, 150-199 |
| 048 | 24 | | PK | | 37-7 | 73-21-11 | D08026P | | 44 | | D08118P | | 4 | | 275-299 |
| 049 | 22 | | PA | | 33-10 | 23-22-11 | D04774P | | 4 | | D05646J | | 10 | | ALL |
| 050 | 20 | | PA | | 20-2 | 27-41-11 | D04774P | | 15 | | D08118P | | 17 | | ALL |
| 051 | 18 | | PA | | 37-7 | 28-22-21 | D08026P | | 3 | DK | D08118P | | 19 | DK | 050-099, 150-154, 156-162, 165-199 |
| 051 | 18 | | PA | | 10-0 | 28-22-21 | SP09730 | | | S | D08118P | | 19 | DK | 155, 163-164, 275-299 |
| 052 | 18 | | PA | | 37-7 | 28-22-21 | D08026P | | 4 | DK | D08118P | | 18 | DK | ALL |
| 053 | 22 | | PA | | 27-10 | 33-16-18 | D08118P | | 20 | | TB0031H | | 16 | 2 | 050-099 |
| 053 | 22 | | PA | | 28-11 | 33-16-18 | D08118P | | 20 | | TB0031H | | 16 | 2 | 150-199, 275-299 |
| 054 | 22 | | PA | | 27-10 | 33-16-18 | D08118P | | 21 | | TB0031H | | 11 | 2 | 050-099 |
| 054 | 22 | | PA | | 28-11 | 33-16-18 | D08118P | | 21 | | TB0031H | | 11 | 2 | 150-199, 275-299 |
| 055 | 22 | | PA | | 27-10 | 33-16-18 | D08118P | | 22 | | TB0031H | | 18 | 2 | 050-099 |
| 055 | 22 | | PA | | 28-11 | 33-16-18 | D08118P | | 22 | | TB0031H | | 18 | 2 | 150-199, 275-299 |
| 056 | 22 | | PA | | 27-10 | 33-16-18 | D08118P | | 23 | | TB0031H | | 11 | 2 | 050-099 |
| 056 | 22 | | PA | | 28-11 | 33-16-18 | D08118P | | 23 | | TB0031H | | 11 | 2 | 150-199, 275-299 |
| 057 | 16 | | PA | | 26-2 | 33-13-18 | D08118P | | 24 | FM | SP02270 | | 9 | | 050-099, 150-155, 162-165, 275-276 |
| 058 | 24 | | PK | | 12-7 | 28-22-11 | D08026P | | 31 | | D04042P | | 3 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0260

Page 4

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0264 | 286T0264 | | | P61 TO L W/W-S2B-FLT CONT/ENG INSTR (continued) | | | | | | | | | | | | | |
| 059 | 24 | | PK | 12-7 | 28-25-11 | D08026P | | 32 | | | | | D04042P | 4 | | | ALL |
| 066 | 22 | | PA | 37-7 | 28-22-21 | D08118P | | 26 | | | | | D08026P | 35 | | | ALL |
| 070 | 20 | | PA | 75-0 | 28-26-11 | D04612J | | 2 | | | | | D08026P | 37 | | | 050-099 |
| 070 | 20 | | PA | 85-0 | 28-26-11 | D04612J | | 2 | | | | | D08026P | 37 | | | 150-199, 275-299 |
| 071 | 20 | | PA | 2-10 | 27-51-41 | D01546 | | 7 | | | | | GD03412 | S.. | E | | ALL |
| 072 | 20 | | PA | 75-0 | 28-26-11 | D04612J | | 3 | | | | | D08026P | 38 | | | 050-099 |
| 072 | 20 | | PA | 85-0 | 28-26-11 | D04612J | | 3 | | | | | D08026P | 38 | | | 150-199, 275-299 |
| 073 | 20 | | PA | 75-0 | 28-26-11 | D04612J | | 1 | | | | | D08026P | 36 | | | 050-099 |
| 073 | 20 | | PA | 85-0 | 28-26-11 | D04612J | | 1 | | | | | D08026P | 36 | | | 150-199, 275-299 |
| 074 | 20 | | PA | 28-10 | 76-11-11 | D04774P | | 27 | | | | | D08026P | 49 | | | ALL |
| 083 | 18 | | PA | 33-10 | SPARE | D05854P | | 4 | | | | | D05646J | 17 | DK | | ALL |
| 084 | 20 | | PA | 72-0 | SPARE | D04774P | | 44 | | | | | D04634J | 16 | | | 050-099 |
| 084 | 20 | | PA | 81-11 | SPARE | D04774P | | 44 | | | | | D04634J | 16 | | | 150-199, 275-299 |
| 085 | 20 | | PA | 75-0 | SPARE | D08026P | | 39 | | | | | D04612J | 8 | | | 050-099 |
| 085 | 20 | | PA | 85-0 | SPARE | D08026P | | 39 | | | | | D04612J | 8 | | | 150-199, 275-299 |
| 086 | 18 | | PA | 38-1 | 78-34-11 | D04774P | | 25 | DL | | | | D04042P | 21 | DK | | ALL |
| 087 | 18 | | PA | 29-2 | 78-34-11 | D06310P | | 8 | DK | | | | D05854P | 19 | DL | | ALL |
| 092 | 24 | | PK | 28-10 | SPARE | D04774P | | 46 | | | | | D08026P | 42 | | | ALL |
| 099 | 20 | | PA | 48-3 | 76-11-11 | D08026P | | 13 | | | | | D04634J | 12 | | | 050-099 |
| 099 | 20 | | PA | 58-8 | 76-11-11 | D08026P | | 13 | | | | | D04634J | 12 | | | 150-199, 275-299 |
| 103 | 24 | | PK | 28-10 | 32-09-11 | D08026P | | 47 | | | | | D04774P | 54 | | | ALL |
| 106 | 20 | | PA | 48-3 | 76-11-11 | D08026P | | 52 | | | | | D04634J | 9 | | | 050-099 |
| 106 | 20 | | PA | 58-8 | 76-11-11 | D08026P | | 52 | | | | | D04634J | 9 | | | 150-199, 275-299 |
| 107 | 24 | | PK | 17-1 | 73-21-15 | D08028P | | 20 | | | | | D04774P | 16 | | | ALL |
| 112 | 24 | | PK | 17-1 | 73-21-18 | D04774P | | 47 | | | | | D08028P | 2 | | | ALL |
| 113 | 24 | | PK | 17-1 | 73-21-18 | D04774P | | 48 | | | | | D08028P | 3 | | | ALL |
| 120 | 24 | | PK | 33-10 | 27-88-11 | D04774P | | 29 | | | | | D05646J | 20 | | | ALL |
| 121 | 24 | | PK | 17-1 | 80-11-11 | D04774P | | 22 | | | | | D08028P | 18 | | | ALL |
| 122 | 24 | | PK | 17-1 | 80-11-11 | D04774P | | 23 | | | | | D08028P | 19 | | | ALL |
| 123 | 24 | | PK | 10-7 | SPARE | D08026P | | 29 | | | | | D05646J | 6 | | | ALL |
| 130 | 24 | | PK | 29-2 | 21-58-12 | D05854P | | 11 | | | | | D06310P | 11 | | | ALL |
| 131 | 24 | | PK | 29-2 | 21-58-12 | D05854P | | 12 | | | | | D06310P | 12 | | | ALL |
| 132 | 24 | | PK | 10-6 | 21-58-12 | D06312J | | 1 | | | | | D06310P | 1 | | | ALL |
| 133 | 24 | | PK | 10-6 | 21-58-12 | D06312J | | 2 | | | | | D06310P | 2 | | | ALL |
| 134 | 24 | | PK | 10-6 | 21-58-12 | D06312J | | 3 | | | | | D06310P | 3 | | | ALL |
| 135 | 24 | | PK | 10-6 | 21-58-12 | D06312J | | 4 | | | | | D06310P | 4 | | | ALL |
| 138 | 24 | | PK | 28-5 | 21-58-14 | D08028P | | 21 | | | | | D06310P | 10 | | | ALL |
| 140 | 24 | | PK | 29-2 | 21-58-16 | D05854P | | 14 | | | | | D06310P | 14 | | | ALL |
| 141 | 22 | | PA | 29-2 | 21-58-16 | D05854P | | 15 | | | | | D06310P | 15 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0260

Page 5

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|--|----|-------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0264 | 286T0264 | P61 TO L W/W-S2B-FLT CONT/ENG INSTR (continued) | | | | | | | | | | | | | |
| 142 | 22 | | PA | 29-2 | 21-58-16 | D05854P | | 16 | | | D06310P | | 16 | | ALL |
| 143 | 24 | | PK | 28-5 | 21-58-16 | D08028P | | 22 | | | D06310P | | 19 | | ALL |
| 144 | 24 | | PK | 28-5 | 21-58-16 | D08028P | | 23 | | | D06310P | | 17 | | ALL |
| 145 | 24 | | PK | 28-5 | 21-58-16 | D08028P | | 24 | | | D06310P | | 18 | | ALL |
| 16A | 22 | | PQ | 16-8 | 28-42-12 | D08026P | | 41 | | | D04042P | | 23 | | 150-154, 275 |
| 16AZ | | | | 0-0 | 28-42-12 | D08026P | | DED | | | D04042P | | DED | | 150-154, 275 |
| 173 | 18 | | PA | 10-10 | 24-11-11 | D06310P | | 23 | DK | | D05646J | | 4 | DK | ALL |
| 177 | 18 | | PA | 38-1 | 78-34-21 | D04774P | | 36 | DL | | D04042P | | 22 | DK | ALL |
| 201B | 22 | | PB | 111-3 | 27-58-21 | D08028P | | 9 | | | D01546 | | 9 | | 050-099 |
| 201B | 22 | | PB | 121-0 | 27-58-21 | D08028P | | 9 | | | D01546 | | 9 | | 150-199, 275-299 |
| 201R | 22 | | PB | 0-0 | 27-58-21 | D08028P | | 10 | | | D01546 | | 8 | | ALL |
| 202B | 22 | | PB | 88-8 | 27-51-41 | D08026P | | 23 | | | D01546 | | 1 | | 050-099 |
| 202B | 22 | | PB | 98-5 | 27-51-41 | D08026P | | 23 | | | D01546 | | 1 | | 150-199, 275-299 |
| 202R | 22 | | PB | 0-0 | 27-51-41 | D08026P | | 24 | | | D01546 | | 2 | | ALL |
| 203B | 22 | | PB | 33-2 | 27-58-21 | D08028P | | 11 | | | D05646J | | 11 | | ALL |
| 203R | 22 | | PB | 0-0 | 27-58-21 | D08028P | | 12 | | | D05646J | | 12 | | ALL |
| 204B | 16 | | PB | 26-2 | 33-13-18 | D08118P | | 25 | FM | | SP04096 | | 9 | | 156-157, 166-199, 277-299 |
| 204R | 16 | | PB | 0-0 | 33-13-18 | D08118P | | 24 | FM | | SP02270 | | 9 | | 156-157, 166-199, 277-299 |
| 301B | 22 | | PC | 111-3 | 27-58-21 | D08028P | | 6 | | | D01546 | | 12 | | 050-099 |
| 301B | 22 | | PC | 121-0 | 27-58-21 | D08028P | | 6 | | | D01546 | | 12 | | 150-199, 275-299 |
| 301R | 22 | | PC | 0-0 | 27-58-21 | D08028P | | 7 | | | D01546 | | 10 | | ALL |
| 301Y | 22 | | PC | 0-0 | 27-58-21 | D08028P | | 8 | | | D01546 | | 11 | | ALL |
| 303B | 24 | | PM | 33-2 | 27-58-21 | D08028P | | 13 | | | D05646J | | 13 | | ALL |
| 303R | 24 | | PM | 0-0 | 27-58-21 | D08028P | | 14 | | | D05646J | | 14 | | ALL |
| 303Y | 24 | | PM | 0-0 | 27-58-21 | D08028P | | 15 | | | D05646J | | 15 | | ALL |
| 402B | 22 | | PD | 88-8 | 27-51-41 | D08026P | | 25 | | | D01546 | | 3 | | 050-099 |
| 402B | 22 | | PD | 98-5 | 27-51-41 | D08026P | | 25 | | | D01546 | | 3 | | 150-199, 275-299 |
| 402G | 22 | | PD | 0-0 | 27-51-41 | D08026P | | 28 | | | D01546 | | 6 | | ALL |
| 402R | 22 | | PD | 0-0 | 27-51-41 | D08026P | | 26 | | | D01546 | | 4 | | ALL |
| 402Y | 22 | | PD | 0-0 | 27-51-41 | D08026P | | 27 | | | D01546 | | 5 | | ALL |
| 658 | 18 | | PA | 16-5 | 28-22-21 | SP09730 | | | S | | D08026P | | 3 | DK | 155, 163-164, 275-299 |
| 810 | 22 | | PA | 33-10 | SPARE | D04774P | | 45 | | | D05646J | | 16 | | 150-199, 275-299 |
| W0265 | 286T0265 | ILS-L COAX,ANT.,G/S L TO FWD PRESS BLKHD | | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-31-11 | D04039P | | =C1 | | | D00017 | | =C1 | | ALL |
| 01CX | | | XE | 4-0 | 34-31-11 | D04039P | | =A1 | | | D00017 | | =A1 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0260
Page 6
Feb 06/2009



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | |
|------------------------|-----------------|----|----|------|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0266 | 286T0266 | | | | P6-TO E3-2-L1-LEFT TRU OUTPUT | | | | | | | | | | |
| 001 | 02 | | PA | | 19-0 | 24-32-11 | T00101 | + | H | | TB5010 | 1 | F | | ALL |
| 002 | 02 | | PA | | 4-0 | 24-32-11 | T00101 | - | G5 | | GD02770 | D.. | G | | ALL |
| W0267 | 286T0267 | | | | COAX,L ILS G/S,E1-3 TO FWD PRESS BLKHD | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-31-11 | D04039J | = | C1 | | D04047P | = | C1 | | ALL |
| 01CX | | | | XE A | 29-0 | 34-31-11 | D04039J | = | A1 | | D04047P | = | A1 | | ALL |
| W0268 | 286T0268 | | | | P6 TO E3-2-R1-RIGHT TRU OUTPUT | | | | | | | | | | |
| 001 | 02 | | PA | | 21-0 | 24-32-11 | T00102 | + | H | | TB5010 | 2 | F | | ALL |
| 002 | 02 | | PA | | 3-0 | 24-32-11 | T00102 | - | G5 | | GD02774 | D.. | G | | ALL |
| W0269 | 286T0269 | | | | ILS-R COAX,ANT.TO FWD PRESS BLKHD,LOC | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-31-21 | D04055P | = | C1 | | D00013 | = | C1 | | ALL |
| 01CX | | | | XE A | 3-0 | 34-31-21 | D04055P | = | A1 | | D00013 | = | A1 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0260
Page 7 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|---|-------|------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0270 | 286T0270 | APU COMPARTMENT-A2-APU SNSR CONTROL | | | | | | | | | | | | | | | |
| 001 | 18 | | HL | | 4-11 | 33-31-31 | D04018P | | 1 | | | | S00428 | 2 | L | | ALL |
| 002 | 18 | | HL | | 3-3 | 33-31-31 | SP01770 | | | 8 | | | S00428 | 3 | L | | ALL |
| 003 | 18 | | HL | | 16-4 | 33-31-31 | SP01772 | | | 8 | | | S00428 | 3 | L | | ALL |
| 004 | 18 | | HL | | 3-8 | 33-31-31 | SP01774 | | | 8 | | | GD01268 | A.. | N | | ALL |
| 005 | 18 | | HL | | 3-8 | 33-31-31 | SP01776 | | | 8 | | | GD01270 | A.. | N | | ALL |
| 201B | 20 | | HQ | B | 7-6 | 24-21-41 | D04018P | | 5 | | | | D00316 | | | | ALL |
| 201R | 20 | | HQ | B | 0-0 | 24-21-41 | D04018P | | 6 | | | | D00316 | | 10 | | ALL |
| 201Z | | | | B | 0-0 | 24-21-41 | D04018P | | 7 | | | | D00316 | DED | | | ALL |
| 301B | 18 | | HN | A | 7-6 | 24-21-41 | D04018P | | 2 | | | | D00316 | | 1 | | ALL |
| 301R | 18 | | HN | A | 0-0 | 24-21-41 | D04018P | | 3 | | | | D00316 | | 6 | | ALL |
| 301Y | 18 | | HN | A | 0-0 | 24-21-41 | D04018P | | 4 | | | | D00316 | | 7 | | ALL |
| 401B | 18 | | HT | C | 7-6 | 24-21-41 | D04018P | | 8 | | | | D00316 | | 12 | | ALL |
| 401G | 18 | | HT | C | 0-0 | 24-21-41 | D04018P | | 9 | | | | D00316 | | 13 | | ALL |
| 401R | 18 | | HT | C | 0-0 | 24-21-41 | D04018P | | 10 | | | | D00316 | | 14 | | ALL |
| 401Y | 18 | | HT | C | 0-0 | 24-21-41 | D04018P | | 11 | | | | D00316 | | 3 | | ALL |
| A-A | | | | | 0-0 | 33-31-31 | L00180 | | | BLK | | | SP01770 | | 8 | | ALL |
| A-B | | | | | 0-0 | 33-31-31 | L00180 | | | WHT | | | SP01774 | | 8 | | ALL |
| A-C | | | | | 0-0 | 33-31-31 | L00181 | | | BLK | | | SP01772 | | 8 | | ALL |
| A-D | | | | | 0-0 | 33-31-31 | L00181 | | | WHT | | | SP01776 | | 8 | | ALL |
| W0271 | 286T0271 | COAX,C ILS LOC,E1-4 TO FWD PRESS BLKHD | | | | | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-31-31 | D04063J | | =C1 | | | | D04059P | | =C1 | | ALL |
| 01CX | | | | XE A | 32-0 | 34-31-31 | D04063J | | =A1 | | | | D04059P | | =A1 | | ALL |
| W0272 | 286T0272 | P6 TO P37-R1-FLT CONT | | | | | | | | | | | | | | | |
| 001 | 14 | | PA | | 20-0 | 27-51-11 | D05860P | | 1 | | | | D05858P | | 1 | | ALL |
| 002 | 14 | | PA | | 20-0 | 27-51-11 | D05860P | | 2 | | | | D05858P | | 2 | | ALL |
| 003 | 14 | | PA | | 20-0 | 27-51-11 | D05860P | | 3 | | | | D05858P | | 3 | | ALL |
| 004 | 18 | | PA | | 12-0 | 27-81-21 | D05862P | | 1 | | | | D05868P | | 1 | | ALL |
| 005 | 18 | | PA | | 12-0 | 27-81-21 | D05862P | | 2 | | | | D05868P | | 2 | | ALL |
| 006 | 18 | | PA | | 12-0 | 27-81-21 | D05862P | | 3 | | | | D05868P | | 3 | | ALL |
| 007 | 20 | | PA | | 12-0 | 27-81-11 | D05862P | | 4 | | | | D05868P | | 4 | | ALL |
| 008 | 20 | | PA | | 12-0 | 27-81-11 | D05862P | | 5 | | | | D05868P | | 5 | | ALL |
| 009 | 20 | | PA | | 12-0 | 27-81-11 | D05862P | | 6 | | | | D05868P | | 6 | | ALL |
| 010 | 12 | | PA | | 20-0 | 24-51-52 | D05860P | | 4 | | | | D05858P | | 4 | | ALL |
| 011 | 12 | | PA | | 20-0 | 24-51-52 | D05860P | | 5 | | | | D05858P | | 5 | | ALL |
| 012 | 12 | | PA | | 20-0 | 24-51-52 | D05860P | | 6 | | | | D05858P | | 6 | | ALL |
| 013 | 12 | | PA | | 20-0 | 24-51-52 | D05860P | | 7 | | | | D05858P | | 7 | | ALL |
| 014 | 18 | | PA | | 20-0 | 25-29-11 | D05860P | | 8 | | | | D05868P | | 7 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0270
 Page 1
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|------|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0272 | 286T0272 | | | P6 TO P37-R1-FLT CONT (continued) | | | | | | | | | | | | |
| 015 | 18 | | PA | 20-0 | 25-29-11 | D05860P | | 9 | | | | D05868P | 8 | | ALL | |
| 018 | 22 | | PA | 13-0 | SPARE | D05960P | | 4 | | | | D05962P | 4 | | 150-154 | |
| 018 | 22 | | PA | 13-0 | 30-71-21 | D05960P | | 4 | | | | D05962P | 4 | | 275 | |
| 019 | 20 | | PA | 13-0 | 30-71-23 | D05960P | | 2 | | | | D05962P | 2 | | 275 | |
| 020 | 20 | | PA | 13-0 | 30-71-23 | D05960P | | 3 | | | | D05962P | 3 | | 275 | |
| 021 | 22 | | PA | 13-0 | SPARE | D05960P | | 8 | | | | D05962P | 1 | | 150-154 | |
| 021 | 22 | | PA | 13-0 | 30-71-22 | D05960P | | 1 | | | | D05962P | 1 | | 275 | |
| 022 | 20 | | PA | 13-0 | 30-71-22 | D05960P | | 5 | | | | D05962P | 5 | | 150-154, 275 | |
| 023 | 20 | | PA | 13-0 | 30-71-22 | D05960P | | 6 | | | | D05962P | 6 | | 275 | |
| 024 | 22 | | PA | 13-0 | SPARE | D05960P | | 6 | | | | D05962P | 8 | | 150-154 | |
| 024 | 22 | | PA | 13-0 | 30-71-22 | D05960P | | 8 | | | | D05962P | 8 | | 275 | |
| 025 | 22 | | PA | 22-0 | 30-31-21 | D05960P | | 9 | | | | D05868P | 9 | | ALL | |
| 026 | 22 | | PA | 22-0 | 30-31-23 | D05960P | | 10 | | | | D05868P | 10 | | ALL | |
| 027 | 20 | | PA | 13-0 | 30-71-23 | D05960P | | 7 | | | | D05962P | 7 | | 275 | |
| 028 | 18 | | PA | 20-0 | 25-29-11 | D05868P | | 11 | | | | D05860P | 10 | | ALL | |
| 10W | 08 | | PA | 24-0 | 24-54-21 | TB5010 | | 4 | F | | | TB5132 | 7 | E | ALL | |
| W0273 | 286T0273 | | | ILS-R COAX,ANT.,G/S R TO FWD PRESS BLKHD | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-31-21 | D04053P | | = C1 | | | | D00021 | = C1 | | ALL | |
| 01CX | | | XE A | 4-0 | 34-31-21 | D04053P | | = A1 | | | | D00021 | = A1 | | ALL | |
| W0274 | 286T0274 | | | P37 TO L WING FS-R1 | | | | | | | | | | | | |
| 001 | 18 | | PA | 57-0 | 27-81-21 | D08064P | | 1 | | | | D04420J | 1 | | 050-099 | |
| 001 | 18 | | PA | 68-0 | 27-81-21 | D08064P | | 1 | | | | D04420J | 1 | | 150-199, 275-299 | |
| 002 | 18 | | PA | 57-0 | 27-81-21 | D08064P | | 2 | | | | D04420J | 2 | | 050-099 | |
| 002 | 18 | | PA | 68-0 | 27-81-21 | D08064P | | 2 | | | | D04420J | 2 | | 150-199, 275-299 | |
| 003 | 18 | | PA | 67-0 | 27-81-21 | D08064P | | 3 | | | | D04420J | 3 | | 050-099 | |
| 003 | 18 | | PA | 68-0 | 27-81-21 | D08064P | | 3 | | | | D04420J | 3 | | 150-199, 275-299 | |
| 004 | 18 | | PA | 23-0 | 27-81-21 | SP01920 | | | 9 | | | D04420J | 4 | | ALL | |
| W0275 | 286T0275 | | | COAX,C ILS G/S,E1-4 TO FWD PRESS BLKHD | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-31-31 | D04061J | | = C1 | | | | D04057P | = C1 | | ALL | |
| 01CX | | | XE A | 32-0 | 34-31-31 | D04061J | | = A1 | | | | D04057P | = A1 | | ALL | |
| W0276 | 286T0276 | | | P11 TO P6-L1-L GEN PWR DISTRIBUTION | | | | | | | | | | | | |
| 001 | 12 | | PA | 16-0 | 24-51-11 | D04086P | | 1 | | | | TB5020 | 1 | E | ALL | |
| 002 | 12 | | PA | 16-0 | 24-51-11 | D04086P | | 2 | | | | TB5020 | 2 | E | ALL | |
| 003 | 12 | | PA | 16-0 | 24-51-11 | D04086P | | 3 | | | | TB5020 | 3 | E | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0270

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0276 | 286T0276 | | | P11 TO P6-L1-L GEN PWR DISTRIBUTION (continued) | | | | | | | | | | | |
| 004 | 12 | | PA | | 16-0 | 24-51-11 | D04086P | | 4 | | TB5020 | 4 | E | | ALL |
| 005 | 12 | | PA | | 16-0 | 24-51-11 | D04086P | | 5 | | TB5020 | 5 | E | | ALL |
| 006 | 12 | | PA | | 16-0 | 24-51-11 | D04086P | | 6 | | TB5020 | 6 | E | | ALL |
| 007 | 10 | | PA | | 16-0 | 24-54-11 | D04088P | | C | | TB5020 | 7 | E | | ALL |
| 008 | 08 | | PA | | 16-0 | 24-54-11 | D04088P | | A | | TB5020 | 8 | E | | ALL |
| 009 | 10 | | PA | | 16-0 | 24-53-11 | D04088P | | B | | TB5020 | 9 | E | | ALL |
| 011 | 12 | | PA | | 16-0 | 24-51-42 | D08128P | | 16 | | TB5152 | 8 | E | | ALL |
| 012 | 12 | | PA | | 16-0 | 24-51-42 | D08128P | | 20 | | TB5152 | 9 | E | | ALL |
| 013 | 12 | | PA | | 17-0 | 24-51-42 | D08128P | | 24 | | TB5020 | 12 | E | | ALL |
| 014 | 20 | | PA | | 15-0 | 24-51-42 | D08128P | | 2 | | TB5022 | 14 | E | | ALL |
| 015 | 20 | | PA | | 15-0 | 24-51-42 | D08128P | | 4 | | TB5022 | 15 | E | | ALL |
| 016 | 20 | | PA | | 15-0 | 24-51-42 | D08128P | | 6 | | TB5022 | 16 | E | | ALL |
| 017 | 12 | | PA | | 16-0 | 24-51-14 | D08128P | | 14 | | TB5152 | 1 | E | | ALL |
| 018 | 18 | | PA | | 16-0 | 24-51-14 | D08128P | | 8 | DL | TB5152 | 2 | E | | ALL |
| 019 | 12 | | PA | | 16-0 | 24-51-14 | D08128P | | 22 | | TB5152 | 3 | E | | ALL |
| 020 | 12 | | PA | | 16-0 | 24-51-14 | TB5152 | | 10 | E | D08128P | 18 | | | 050-099 |
| 020 | 12 | | PA | | 16-0 | 24-51-14 | D08128P | | 18 | | TB5152 | 10 | E | | 150-199, 275-299 |
| W0277 | 286T0277 | | | ILS-C COAX,ANT.TO FWD PRESS BLKHD,LOC | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-31-31 | D04063P | | =C1 | | D00015 | =C1 | | | ALL |
| 01CX | | | | XE A | 4-0 | 34-31-31 | D04063P | | =A1 | | D00015 | =A1 | | | ALL |
| W0278 | 286T0278 | | | P6 TO P11-S1-STBY PWR DISTRIBUTION | | | | | | | | | | | |
| 001 | 12 | | PA | | 18-0 | 24-54-73 | D04096P | | 16 | | TB5020 | 11 | E | | ALL |
| 002 | 18 | | PA | | 16-0 | 24-51-31 | D04096P | | 18 | | TB5022 | 12 | E | | ALL |
| 003 | 22 | | PA | | 16-0 | 24-51-31 | D04096P | | 1 | | TB5022 | 11 | E | | ALL |
| 004 | 14 | | PA | | 18-0 | 24-54-73 | D04096P | | 14 | | TB5020 | 10 | E | | ALL |
| 005 | 24 | | PK | | 18-0 | 24-51-31 | D04096P | | 2 | | TB5020 | 13 | E | | ALL |
| 006 | 08 | | PA | | 16-0 | 24-54-71 | D04094P | | A | | TB5022 | 13 | E | | ALL |
| W0279 | 286T0279 | | | COAX,R ILS LOC,E1-5 TO FWD PRESS BLKHD | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-31-21 | D04049P | | =C1 | | D04055J | =C1 | | | ALL |
| 01CX | | | | XE A | 32-0 | 34-31-21 | D04049P | | =A1 | | D04055J | =A1 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0270
Page 3 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|------|--|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0280 | 286T0280 | | | | P6 TO P11-R1-R GEN PWR DISTRIBUTION | | | | | | | | | | | | |
| 001 | 12 | PA | | 15-0 | 24-51-52 | D04090P | | | | | | | TB5022 | 1 | E | | ALL |
| 002 | 08 | PA | | 15-0 | 24-54-21 | D04092P | | | | | | | TB5022 | 8 | E | | ALL |
| 003 | 08 | PA | | 15-0 | 24-54-21 | D04092P | | | | | | | TB5022 | 9 | E | | ALL |
| 004 | 10 | PA | | 15-0 | 24-53-21 | D04092P | | | | | | | TB5022 | 10 | E | | ALL |
| 005 | 12 | PA | | 15-0 | 24-51-21 | D04090P | | | | | | | TB5022 | 2 | E | | ALL |
| 006 | 12 | PA | | 15-0 | 24-51-21 | D04090P | | | | | | | TB5022 | 3 | E | | ALL |
| 007 | 12 | PA | | 15-0 | 24-51-21 | D04090P | | | | | | | TB5022 | 4 | E | | ALL |
| 008 | 14 | PA | | 15-0 | 24-51-21 | D04090P | | | | | | | TB5022 | 5 | E | | ALL |
| 009 | 14 | PA | | 15-0 | 24-51-21 | D04090P | | | | | | | TB5022 | 6 | E | | ALL |
| 010 | 14 | PA | | 15-0 | 24-51-21 | D04090P | | | | | | | TB5022 | 7 | E | | ALL |
| 011 | 20 | PA | | 18-0 | 24-51-43 | D06430P | | | | | | | TB0292F | C005 | 2 | | 050-099 |
| 011 | 20 | PA | | 16-0 | 24-51-43 | D06430P | | | | | | | TB0292F | C005 | 2 | | 150-199, 275-299 |
| 012 | 20 | PA | | 18-0 | 24-51-43 | D06430P | | | | | | | TB0292F | C006 | 2 | | 050-099 |
| 012 | 20 | PA | | 16-0 | 24-51-43 | D06430P | | | | | | | TB0292F | C006 | 2 | | 150-199, 275-299 |
| 013 | 20 | PA | | 19-0 | 24-51-43 | D06430P | | | | | | | TB5020 | 16 | E | | 050-099 |
| 013 | 20 | PA | | 17-0 | 24-51-43 | D06430P | | | | | | | TB5020 | 16 | E | | 150-199, 275-299 |
| 014 | 20 | PA | | 18-0 | 24-51-43 | D06430P | | | | | | | TB0292F | C002 | 2 | | 050-099 |
| 014 | 20 | PA | | 16-0 | 24-51-43 | D06430P | | | | | | | TB0292F | C002 | 2 | | 150-199, 275-299 |
| 015 | 20 | PA | | 18-0 | 24-51-43 | D06430P | | | | | | | TB0292F | C003 | 2 | | 050-099 |
| 015 | 20 | PA | | 16-0 | 24-51-43 | D06430P | | | | | | | TB0292F | C003 | 2 | | 150-199, 275-299 |
| 016 | 20 | PA | | 18-0 | 24-51-43 | D06430P | | | | | | | TB0292F | C004 | 2 | | 050-099 |
| 016 | 20 | PA | | 16-0 | 24-51-43 | D06430P | | | | | | | TB0292F | C004 | 2 | | 150-199, 275-299 |
| 017 | 12 | PA | | 18-0 | 24-51-24 | D06430P | | | | | | | TB5152 | 5 | E | | 050-099 |
| 017 | 12 | PA | | 16-0 | 24-51-24 | D06430P | | | | | | | TB5152 | 5 | E | | 150-199, 275-299 |
| 018 | 12 | PA | | 18-0 | 24-51-24 | D06430P | | | | | | | TB5152 | 4 | E | | 050-099 |
| 018 | 12 | PA | | 16-0 | 24-51-24 | D06430P | | | | | | | TB5152 | 4 | E | | 150-199, 275-299 |
| 019 | 18 | PA | | 18-0 | 24-51-24 | D06430P | | | | | | | TB5152 | 6 | E | | 050-099 |
| 019 | 18 | PA | | 16-0 | 24-51-24 | D06430P | | | | | | | TB5152 | 6 | E | | 150-199, 275-299 |
| 020 | 12 | PA | | 18-0 | 24-51-24 | D06430P | | | | | | | TB5152 | 7 | E | | 050-099 |
| 020 | 12 | PA | | 16-0 | 24-51-24 | D06430P | | | | | | | TB5152 | 7 | E | | 150-199, 275-299 |
| W0281 | 286T0281 | | | | ILS-C COAX,ANT.TO FWD PRESS BLKHD,G/S | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-31-31 | D04061P | | | | | | | D00019 | | = C1 | | ALL |
| 01CX | | | XE A | 4-0 | 34-31-31 | D04061P | | | | | | | D00019 | | = A1 | | ALL |
| W0282 | 286T0282 | | | | F1 TO FWD CHILLER-R1-CHILLER POWER | | | | | | | | | | | | |
| 001 | 16 | PA | | 13-0 | 25-33-11 | D02660 | | | | | | | D02654 | 1 | | | ALL |
| 002 | 16 | PA | | 13-0 | 25-33-11 | D02660 | | | | | | | D02654 | 2 | | | ALL |
| 003 | 16 | PA | | 13-0 | 25-33-11 | D02660 | | | | | | | D02654 | 3 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0280

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|---|------|-------|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0282 | 286T0282 | F1 TO FWD CHILLER-R1-CHILLER POWER (continued) | | | | | | | | | | | | | |
| 004 | 24 | | PK | 13-0 | 25-33-11 | D02660 | | 4 | | D02654 | | 4 | | | ALL |
| 007 | 20 | | PA | 13-0 | 25-33-11 | D02660 | | 7 | | D02654 | | 7 | | | ALL |
| 011 | 20 | | PA | 5-0 | 25-33-11 | D02654 | | 5 | | GD01892 | | D.. | E | | 050-099, 150-199, 277-278 |
| 011 | 20 | | PA | 5-0 | 25-33-11 | D02654 | | 6 | | GD01892 | | D.. | E | | 275-276, 280-299 |
| 012 | 20 | | PA | 5-0 | 25-33-11 | D02654 | | 8 | | GD01892 | | D.. | E | | ALL |
| 013 | 16 | | PA | 4-0 | 25-33-11 | D02654 | | 9 | | GD01898 | | S.. | E | | ALL |
| 022 | 22 | | PA | 19-0 | 25-33-11 | D02660 | | 5 | | SP02594 | | | 9 | | 150-154, 275-276 |
| 022 | 22 | | PA | 13-0 | 25-33-11 | D02660 | | 5 | | D02654 | | 6 | | | 277-278 |
| 022 | 22 | | PA | 13-0 | 25-33-11 | D02660 | | 5 | | D02654 | | 5 | | | 280-299 |
| 023 | 22 | | PA | 13-0 | 25-33-11 | D02654 | | 6 | | D02660 | | 5 | | | 050-099, 155-199 |
| 023 | 22 | | PA | 11-0 | 25-33-11 | D02654 | | 6 | | SP02596 | | | 9 | | 150-154 |
| 023 | 22 | | PA | 11-0 | 25-33-11 | D02654 | | 5 | | SP02596 | | | 9 | | 275-276 |
| 105 | 20 | | PA | 21-0 | 33-24-14 | D02660 | | 10 | | SP03140 | | | 9 | | 275-299 |
| 106 | 20 | | PA | 4-0 | SPARE | D02660 | | 9 | | GD01820 | | A.. | G | | 150-199 |
| 106 | 20 | | PA | 4-0 | 33-24-14 | D02660 | | 9 | | GD01820 | | A.. | G | | 275-299 |
| 107 | 20 | | PA | 21-0 | 33-24-14 | D02660 | | 8 | | SP03138 | | | 9 | | 275-299 |
| W0283 | 286T0283 | COAX,R ILS G/S,E1-5 TO FWD PRESS BLKHD | | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-31-21 | D04053J | | =C1 | | D04051P | | =C1 | | | ALL |
| 01CX | | | XE A | 32-0 | 34-31-21 | D04053J | | =A1 | | D04051P | | =A1 | | | ALL |
| W0284 | 286T0284 | A2 TO L AFT CHILLER-L1-CHILLER POWER | | | | | | | | | | | | | |
| 004 | 24 | | PK | 23-10 | 25-33-11 | D02656 | | 4 | | D02650 | | 4 | | | ALL |
| 007 | 20 | | PA | 23-10 | 25-33-11 | D02656 | | 7 | | D02650 | | 7 | | | ALL |
| 011 | 20 | | PA | 2-2 | 25-33-11 | D02650 | | 5 | | GD01890 | | D.. | E | | 050-099, 150-199, 275-278 |
| 011 | 20 | | PA | 2-2 | 25-33-11 | D02650 | | 6 | | GD01890 | | D.. | E | | 280-299 |
| 012 | 20 | | PA | 2-2 | 25-33-11 | D02650 | | 8 | | GD01890 | | D.. | E | | ALL |
| 018 | 14 | | PA | 23-10 | 25-33-11 | D02650 | | 1 | FO | D02656 | | 1 | FN | | ALL |
| 019 | 14 | | PA | 23-10 | 25-33-11 | D02650 | | 2 | FO | D02656 | | 2 | FN | | 050-099, 150-199 |
| 019 | 14 | | PA | 23-10 | 25-33-11 | D02656 | | 2 | FN | D02650 | | 2 | FO | | 275-299 |
| 020 | 14 | | PA | 23-10 | 25-33-11 | D02650 | | 3 | FO | D02656 | | 3 | FN | | 050-099, 150-199 |
| 020 | 14 | | PA | 23-10 | 25-33-11 | D02656 | | 3 | FN | D02650 | | 3 | FO | | 275-299 |
| 021 | 14 | | PA | 2-2 | 25-33-11 | D02650 | | 9 | FO | GD01896 | | S.. | E | | ALL |
| 022 | 20 | | PA | 23-10 | 25-33-11 | D02656 | | 5 | | D02650 | | 6 | | | 050-099, 150-199, 275-278 |
| 022 | 20 | | PA | 23-10 | 25-33-11 | D02656 | | 5 | | D02650 | | 5 | | | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0280
Page 2
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|-------|------|------------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0285 | 286T0285 | | | LRRA-L COAX,ANT.,XMTR & RCVR | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-33-11 | D00401B | = C71 | | | | D00023 | = C1 | | ALL | | |
| 01CX | | 65 | A | 0-0 | 34-33-11 | D00401B | 71 | | | | D00023 | = A1 | | ALL | | |
| 02CO | | | B | 0-0 | 34-33-11 | D00401A | = C71 | | | | D00025 | = C1 | | ALL | | |
| 02CX | | 65 | B | 0-0 | 34-33-11 | D00401A | 71 | | | | D00025 | = A1 | | ALL | | |
| W0286 | 286T0286 | | | A3 TO R AFT CHILLER-R1-CHILLER POWER | | | | | | | | | | | | |
| 004 | 24 | | PK | 20-10 | 25-33-11 | D02658 | | 4 | | | D02652 | 4 | | ALL | | |
| 011 | 20 | | UA | 21-0 | 25-33-11 | D02652 | | 5 | | | GD01888 | D.. E | *2 | 050-099, 150-199 | | |
| 011 | 20 | | PA | 21-0 | 25-33-11 | D02652 | | 5 | | | GD01888 | D.. E | | 275-276 | | |
| 011 | 20 | | PA | 8-9 | 25-33-11 | D02652 | | 5 | | | GD00066 | D.. 2 | | 277-278 | | |
| 011 | 20 | | PA | 8-9 | 25-33-11 | D02652 | | 6 | | | GD00066 | D.. 2 | | 280-299 | | |
| 012 | 20 | | UA | 21-0 | 25-33-11 | D02652 | | 8 | | | GD01888 | D.. E | *2 | 050-099, 150-199 | | |
| 012 | 20 | | PA | 21-0 | 25-33-11 | D02652 | | 8 | | | GD01888 | D.. E | | 275-276 | | |
| 012 | 20 | | PA | 8-9 | 25-33-11 | D02652 | | 8 | | | GD00066 | D.. 2 | | 277-299 | | |
| 018 | 14 | | PA | 20-10 | 25-33-11 | D02652 | | 1 | FO | | D02658 | 1 FN | | 050-099, 150-199 | | |
| 018 | 14 | | PA | 20-10 | 25-33-11 | D02658 | | 1 | FN | | D02652 | 1 FO | | 275-299 | | |
| 019 | 14 | | PA | 20-10 | 25-33-11 | D02652 | | 2 | FO | | D02658 | 2 FN | | 050-099, 150-199 | | |
| 019 | 14 | | PA | 20-10 | 25-33-11 | D02658 | | 2 | FN | | D02652 | 2 FO | | 275-299 | | |
| 020 | 14 | | PA | 20-10 | 25-33-11 | D02652 | | 3 | FO | | D02658 | 3 FN | | 050-099, 150-199 | | |
| 020 | 14 | | PA | 20-10 | 25-33-11 | D02658 | | 3 | FN | | D02652 | 3 FO | | 275-299 | | |
| 021 | 14 | | PA | 5-5 | 25-33-11 | D02652 | | 9 | FO | | GD01896 | S.. E | | ALL | | |
| 025 | 20 | | PA | 20-10 | 25-33-11 | D02658 | | 7 | | | D02652 | 7 | | ALL | | |
| 026 | 20 | | PA | 20-10 | 25-33-11 | D02658 | | 5 | | | D02652 | 6 | | 050-099, 150-199, 275-278 | | |
| 026 | 20 | | PA | 20-10 | 25-33-11 | D02658 | | 5 | | | D02652 | 5 | | 280-299 | | |
| W0288 | 286T0288 | | | P31 TO R ELEC HYD PUMP L1-115 VAC POWER DISTRIBUTION | | | | | | | | | | | | |
| 001 | 08 | | HA | 3-0 | 29-11-22 | SM00001 | | | GE | | D00486 | A | | 050-099 | | |
| 001 | 08 | | HA | 2-2 | 29-11-22 | SM00001 | | | GE | | D00486 | A | | 150-199, 275-299 | | |
| 002 | 08 | | HA | 3-0 | 29-11-22 | SM00002 | | | GE | | D00486 | B | | 050-099 | | |
| 002 | 08 | | HA | 2-2 | 29-11-22 | SM00002 | | | GE | | D00486 | B | | 150-199, 275-299 | | |
| 003 | 08 | | HA | 3-0 | 29-11-22 | SM00003 | | | GE | | D00486 | C | | 050-099 | | |
| 003 | 08 | | HA | 2-2 | 29-11-22 | SM00003 | | | GE | | D00486 | C | | 150-199, 275-299 | | |
| 008 | 06 | | QY | 95-3 | 29-11-22 | M00896 | | A2 | H6 | | SM00001 | GE | | 050-099 | | |
| 008 | 06 | | QY | 104-7 | 29-11-22 | M00896 | | A2 | H6 | | SM00001 | GE | | 150-199, 275-299 | | |
| 009 | 06 | | QY | 95-3 | 29-11-22 | M00896 | | B2 | H6 | | SM00002 | GE | | 050-099 | | |
| 009 | 06 | | QY | 104-7 | 29-11-22 | M00896 | | B2 | H6 | | SM00002 | GE | | 150-199, 275-299 | | |
| 010 | 06 | | QY | 95-3 | 29-11-22 | M00896 | | C2 | H6 | | SM00003 | GE | | 050-099 | | |
| 010 | 06 | | QY | 104-7 | 29-11-22 | M00896 | | C2 | H6 | | SM00003 | GE | | 150-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0280

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0288 | 286T0288 | | | P31 TO R ELEC HYD PUMP L1-115 VAC POWER DISTRIBUTION (continued) | | | | | | | | | | | | |
| 011 | 18 | | UA | | 101-0 | 29-32-11 | TB0030F | A001 | 2 | | SP02242 | | | | 9 | 050-099 |
| 011 | 18 | | UA | | 111-7 | 29-32-11 | TB0030F | A001 | 2 | | SP02242 | | | | 9 | 150-199, 275-299 |
| 014 | 10 | | HA | | 7-0 | 29-11-22 | GD03508 | S.. | E* | | D00486 | | D | | | 050-099 |
| 014 | 10 | | HA | | 7-2 | 29-11-22 | GD03508 | S.. | E* | | D00486 | | D | | | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0280
Page 4 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|---|-------|-------|-------------|---------|-------|-------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0290 | 286T0290 | P32 TO ELEC HYD PUMP L-R1-115 VAC POWER DISTRIBUTION | | | | | | | | | | | | | | |
| 001 | 08 | | HA | 1-5 | 29-11-12 | SM00006 | | GE | | D00480 | | A | | 050-099 | | |
| 001 | 08 | | HA | 1-6 | 29-11-12 | SM00006 | | GE | | D00480 | | A | | 150-199, 275-278 | | |
| 001 | 08 | | HA | 3-0 | 29-11-12 | SM00006 | | GE | | D00480 | | A | | 280-299 | | |
| 002 | 08 | | HA | 1-5 | 29-11-12 | SM00007 | | GE | | D00480 | | B | | 050-099 | | |
| 002 | 08 | | HA | 1-6 | 29-11-12 | SM00007 | | GE | | D00480 | | B | | 150-199, 275-278 | | |
| 002 | 08 | | HA | 3-0 | 29-11-12 | SM00007 | | GE | | D00480 | | B | | 280-299 | | |
| 003 | 08 | | HA | 1-5 | 29-11-12 | SM00008 | | GE | | D00480 | | C | | 050-099 | | |
| 003 | 08 | | HA | 1-6 | 29-11-12 | SM00008 | | GE | | D00480 | | C | | 150-199, 275-278 | | |
| 003 | 08 | | HA | 3-0 | 29-11-12 | SM00008 | | GE | | D00480 | | C | | 280-299 | | |
| 007 | 08 | | HA | 4-4 | 29-11-12 | GD03512 | | S.. | E* | D00480 | | D | | ALL | | |
| 008 | 06 | | QY | 88-7 | 29-11-12 | M00895 | | A2 | H6 | SM00006 | | GE | | 050-099 | | |
| 008 | 06 | | QY | 98-6 | 29-11-12 | M00895 | | A2 | H6 | SM00006 | | GE | | 150-199, 275-278 | | |
| 008 | 06 | | QY | 100-0 | 29-11-12 | M00895 | | A2 | H6 | SM00006 | | GE | | 280-299 | | |
| 009 | 06 | | QY | 88-7 | 29-11-12 | M00895 | | B2 | H6 | SM00007 | | GE | | 050-099 | | |
| 009 | 06 | | QY | 98-6 | 29-11-12 | M00895 | | B2 | H6 | SM00007 | | GE | | 150-199, 275-278 | | |
| 009 | 06 | | QY | 100-0 | 29-11-12 | M00895 | | B2 | H6 | SM00007 | | GE | | 280-299 | | |
| 010 | 06 | | QY | 88-7 | 29-11-12 | M00895 | | C2 | H6 | SM00008 | | GE | | 050-099 | | |
| 010 | 06 | | QY | 98-6 | 29-11-12 | M00895 | | C2 | H6 | SM00008 | | GE | | 150-199, 275-278 | | |
| 010 | 06 | | QY | 100-0 | 29-11-12 | M00895 | | C2 | H6 | SM00008 | | GE | | 280-299 | | |
| 012 | 20 | | UA | 90-2 | 29-32-11 | TB0032F | | A002 | 2 | SP02244 | | 9 | | 050-099 | | |
| 012 | 20 | | UA | 100-2 | 29-32-11 | TB0032F | | A002 | 2 | SP02244 | | 9 | | 150-199, 275-299 | | |
| W0293 | 286T0293 | LRRA-R COAX,ANT.,XMTR & RCVR | | | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-33-21 | D00403B | | = C71 | | D00027 | | = C1 | | ALL | | |
| 01CX | | 65 | A | 0-0 | 34-33-21 | D00403B | | 71 | | D00027 | | = A1 | | ALL | | |
| 02CO | | | B | 0-0 | 34-33-21 | D00403A | | = C71 | | D00029 | | = C1 | | ALL | | |
| 02CX | | 65 | B | 0-0 | 34-33-21 | D00403A | | 71 | | D00029 | | = A1 | | ALL | | |
| W0296 | 286T0296 | P31 TO P36 | | | | | | | | | | | | | | |
| 001 | 08 | | PA | 10-0 | 24-51-12 | TB5032 | | 1 | E | TB5130 | | 1 | E | ALL | | |
| 002 | 08 | | PA | 10-0 | 24-51-12 | TB5032 | | 2 | E | TB5130 | | 2 | E | ALL | | |
| 003 | 08 | | PA | 10-0 | 24-51-12 | TB5032 | | 3 | E | TB5130 | | 3 | E | ALL | | |
| 016 | 08 | | PA | 10-0 | 24-51-13 | K00119 | | A2 | E | TB5130 | | 4 | E | ALL | | |
| 017 | 08 | | PA | 10-0 | 24-51-13 | K00119 | | B2 | E | TB5130 | | 5 | E | ALL | | |
| 018 | 08 | | PA | 10-0 | 24-51-13 | K00119 | | C2 | E | TB5130 | | 6 | E | ALL | | |
| W0298 | 286T0298 | P32 TO P37 | | | | | | | | | | | | | | |
| 001 | 08 | | PA | 9-6 | 24-51-22 | TB5034 | | 4 | E | TB5132 | | 1 | E | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0290

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|--------|------|------|--------|-------|--------|------|--------|-------------|-----|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0298 | 286T0298 | | | P32 TO P37 (continued) | | | | | | | | | | | | |
| 002 | 08 | PA | | | 9-6 | 24-51-22 | TB5034 | | 5 | E | | TB5132 | | 2 | E | ALL |
| 003 | 08 | PA | | | 9-6 | 24-51-22 | TB5034 | | 6 | E | | TB5132 | | 3 | E | ALL |
| 019 | 08 | PA | | | 9-0 | 24-51-23 | K00120 | | A2 | E | | TB5132 | | 4 | E | ALL |
| 020 | 08 | PA | | | 9-0 | 24-51-23 | K00120 | | B2 | E | | TB5132 | | 5 | E | ALL |
| 021 | 08 | PA | | | 9-5 | 24-51-23 | K00120 | | C2 | E | | TB5132 | | 6 | E | ALL |

WIRE LIST
D280T132

91-21-11
Section W0290
Page 2 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0301 | 286T0301 | | | LRRA-C COAX,ANT.,XMTR & RCVR | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-33-31 | D00405B | =C71 | | | D00031 | =C1 | | | ALL |
| 01CX | | | 65 | A | 0-0 | 34-33-31 | D00405B | 71 | | | D00031 | =A1 | | | ALL |
| 02CO | | | | B | 0-0 | 34-33-31 | D00405A | =C71 | | | D00033 | =C1 | | | ALL |
| 02CX | | | 65 | B | 0-0 | 34-33-31 | D00405A | 71 | | | D00033 | =A1 | | | ALL |
| W0304 | 286T0304 | | | P31 TO A3-L2-R AFT GALLEY CONTROL | | | | | | | | | | | |
| 001 | 24 | | | PK | 25-8 | 25-31-31 | SP03660 | | S | | D00596 | 4 | | | 050-099, 150-199 |
| 001 | 24 | | | PK | 155-2 | 25-31-31 | D06380P | 1 | | | D00596 | 4 | | | 275-278 |
| 001 | 24 | | | PK | 155-0 | 25-31-31 | D06380P | 8 | | | D00596 | 4 | | | 280-299 |
| 002 | 24 | | | PK | 25-8 | 25-31-31 | SP03662 | | S | | D00596 | 5 | | | 050-099, 150-199 |
| 002 | 24 | | | PK | 155-2 | 25-31-31 | D06380P | 2 | | | D00596 | 5 | | | 275-278 |
| 002 | 24 | | | PK | 155-0 | 25-31-31 | D06380P | 5 | | | D00596 | 5 | | | 280-299 |
| 003 | 24 | | | PK | 25-8 | 25-31-31 | SP03664 | | S | | D00596 | 6 | | | 050-099, 150-199 |
| 003 | 24 | | | PK | 155-2 | 25-31-31 | D06380P | 3 | | | D00596 | 6 | | | 275-278 |
| 003 | 24 | | | PK | 155-0 | 25-31-31 | D06380P | 6 | | | D00596 | 6 | | | 280-299 |
| 004 | 24 | | | PK | 25-8 | 25-31-31 | SP03666 | | S | | D00596 | 7 | | | 050-099, 150-199 |
| 004 | 24 | | | PK | 155-2 | 25-31-31 | D06380P | 5 | | | D00596 | 7 | | | 275-278 |
| 004 | 24 | | | PK | 155-0 | 25-31-31 | D06380P | 9 | | | D00596 | 7 | | | 280-299 |
| 005 | 20 | | | PA | 1-7 | 25-31-31 | D00596 | 9 | | | GD01888 | D.. | E | | 050-099, 150-199 |
| 007 | 20 | | | PA | 25-8 | 25-31-31 | D00596 | 10 | | | SP03658 | | S | | 050-099, 150-199 |
| 008 | 22 | | | PA | 26-8 | 33-27-11 | D00596 | 8 | | | SP00728 | | 9 | | 275-278 |
| 008 | 22 | | | PA | 27-0 | 33-27-11 | D00596 | 8 | | | SP00728 | | 9 | | 280-299 |
| 009 | 22 | | | PA | 26-8 | 33-27-11 | D00596 | 11 | | | SP00726 | | 9 | | 275-278 |
| 009 | 22 | | | PA | 27-0 | 33-27-11 | D00596 | 11 | | | SP00726 | | 9 | | 280-299 |
| 010 | 20 | | | PA | 1-7 | 33-27-11 | D00596 | 12 | | | GD01876 | A.. | G | | 275-278 |
| 010 | 20 | | | PA | 2-0 | 33-27-11 | D00596 | 12 | | | GD01876 | A.. | G | | 280-299 |
| 011 | 16 | | | PA | 0-12 | 25-31-31 | D00596 | 10 | FM | | SM00003 | | S | | 275-299 |
| 012 | 16 | | | PA | 1-7 | 25-31-31 | D00596 | 9 | FM | | GD01888 | D.. | E | | 275-278 |
| 012 | 16 | | | PA | 3-0 | 25-31-31 | D00596 | 9 | FM | | GD01888 | D.. | E | | 280-299 |
| 013 | 12 | | | PA | 153-3 | 25-31-31 | SM00001 | | S | | SM00003 | | S | | 275-278 |
| 013 | 12 | | | PA | 153-0 | 25-31-31 | SM00001 | | S | | SM00003 | | S | | 280-299 |
| 014 | 16 | | | PA | 0-12 | 25-31-31 | D06380P | 10 | | | SM00001 | | S | | 275-299 |
| 016 | 18 | | | PA | 25-8 | 30-71-25 | SP03790 | | 9 | | D00596 | 11 | DK | | 050-099, 150-199 |
| 017 | 18 | | | PA | 1-7 | 30-71-25 | D00596 | 12 | DK | | GD05758 | A.. | E | | 050-099, 150-199 |
| 020 | 16 | | | PA | 4-6 | 33-51-12 | D00596 | 1 | FM | | SP00650 | | S | | 275-278 |
| 020 | 16 | | | PA | 6-0 | 33-51-12 | D00596 | 1 | FM | | SP00650 | | S | | 280-299 |
| 021 | 16 | | | PA | 1-7 | 33-51-12 | D00596 | 2 | FM | | GD01888 | D.. | E | | 275-278 |
| 021 | 16 | | | PA | 3-0 | 33-51-12 | D00596 | 2 | FM | | GD01888 | D.. | E | | 280-299 |
| 024 | 18 | | | PA | 3-0 | SPARE | D00596 | CAP | Y | | GD01888 | D.. | E | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0300

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|-------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0304 | 286T0304 | | | P31 TO A3-L2-R AFT GALLEY CONTROL (continued) | | | | | | | | | | | |
| 036 | 18 | | PA | | 27-0 | SPARE | D00596 | CAP | Y | | SP05306 | | S | | 280-299 |
| W0308 | 286T0308 | | | P31 TO A3-L1-R AFT GALLEY POWER FEEDER | | | | | | | | | | | |
| 001 | 06 | | QY | | 151-8 | 25-31-31 | M00226 | A2 | H6 | | SM00001 | | GE | | 275-299 |
| 002 | 06 | | QY | | 151-8 | 25-31-31 | M00226 | B2 | H6 | | SM00002 | | GE | | 275-299 |
| 003 | 06 | | QY | | 151-8 | 25-31-31 | M00226 | C2 | H6 | | SM00003 | | GE | | 275-299 |
| 004 | 04 | | HA | | 26-6 | 25-31-31 | D00594 | | A | | TB0253 | 1 | F | | 050-099, 150-199 |
| 004 | 08 | | HA | | 3-2 | 25-31-31 | D00594 | | A | | SM00001 | | GE | | 275-299 |
| 005 | 04 | | HA | | 26-6 | 25-31-31 | D00594 | | B | | TB0253 | 2 | F | | 050-099, 150-199 |
| 005 | 08 | | HA | | 3-2 | 25-31-31 | D00594 | | B | | SM00002 | | GE | | 275-299 |
| 006 | 04 | | HA | | 26-6 | 25-31-31 | D00594 | | C | | TB0253 | 3 | F | | 050-099, 150-199 |
| 006 | 08 | | HA | | 3-2 | 25-31-31 | D00594 | | C | | SM00003 | | GE | | 275-299 |
| 007 | 04 | | HA | | 1-4 | 25-31-31 | D00594 | | D | | GD01876 | | A.. G | | 050-099, 150-199 |
| 007 | 08 | | HA | | 1-4 | 25-31-31 | D00594 | | D | | GD01876 | | A.. G | | 275-299 |
| W0309 | 286T0309 | | | MKR BCN,SHELF TO ANT. DISC | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-32-11 | D04069J | = | C1 | | D04071J | = | C1 | | ALL |
| 01CX | | | | BR A | 42-0 | 34-32-11 | D04069J | = | A1 | | D04071J | = | A1 | | 050-099 |
| 01CX | | | | BR A | 41-0 | 34-32-11 | D04069J | = | A1 | | D04071J | = | A1 | | 150-199, 275-299 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0311 | 286T0311 | | | VOR-L COAX,SHELF TO ANT. DISC | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-51-11 | D04073J | = C1 | | | D04075P | = C1 | | | ALL | |
| 01CX | | BS | A | 127-0 | 34-51-11 | D04073J | = A1 | | | D04075P | = A1 | | | 050-099 | |
| 01CX | | BS | A | 149-0 | 34-51-11 | D04073J | = A1 | | | D04075P | = A1 | | | 150-199, 275-299 | |
| W0313 | 286T0313 | | | VOR-L COAX,THRU PRESS. SEAL,ANT. | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-51-11 | D04075J | = C1 | | | D00035 | = C1 | | | ALL | |
| 01CX | | BS | A | 54-0 | 34-51-11 | D04075J | = A1 | | | D00035 | = A1 | | | 050-099, 150-154, 162-164, 275-276 | |
| 01CX | | 65 | A | 54-0 | 34-51-11 | D04075J | = A1 | | | D00035 | = A1 | | | 155-157, 165-199, 277-299 | |
| W0315 | 286T0315 | | | VOR-R COAX,SHELF TO ANT. DISC | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-51-21 | D04077J | = C1 | | | D04079P | = C1 | | | ALL | |
| 01CX | | BS | A | 124-11 | 34-51-21 | D04077J | = A1 | | | D04079P | = A1 | | | 050-099 | |
| 01CX | | BS | A | 146-5 | 34-51-21 | D04077J | = A1 | | | D04079P | = A1 | | | 150-199, 275-299 | |
| W0317 | 286T0317 | | | VOR-R COAX,THRU PRESS. SEAL,ANT. | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-51-21 | D04079J | = C1 | | | D00037 | = C1 | | | ALL | |
| 01CX | | BS | A | 54-6 | 34-51-21 | D04079J | = A1 | | | D00037 | = A1 | | | 050-099, 150-154, 162-164, 275-276 | |
| 01CX | | 65 | A | 54-6 | 34-51-21 | D04079J | = A1 | | | D00037 | = A1 | | | 155-157, 165-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W0310
Page 1 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | |
|--------------|-----------------|----|----|-------------|---|----------|---------|--------|-------|---------|------|--------|-------------|------------------------------|
| | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | |
| W0323 | 286T0323 | | | | ATC-R COAX,SHELF TO ANT. DISC,BOTTOM | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-53-13 | D02199 | = C1 | | D04087J | = C1 | | | ALL |
| 01CX | | | JB | A | 16-0 | 34-53-13 | D02199 | = A1 | | D04087J | = A1 | | | 050-099, 155-199, 275-299 |
| 01CX | | | JB | A | 19-0 | 34-53-13 | D02199 | = A1 | | D04087J | = A1 | | | 150-154 |
| W0325 | 286T0325 | | | | ATC-R COAX,ANT.,BOTTOM | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-53-13 | D04087P | = C1 | | D00041 | = C1 | | | ALL |
| 01CX | | | JB | A | 1-8 | 34-53-13 | D04087P | = A1 | | D00041 | = A1 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0320
Page 1 End
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-------------|-----------------|-------|-----|-------------|--|---------|------|------|---------|-------|------|------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0333 | | 286T0333 | | | | ATC-R COAX,SHELF TO TOP ANT.DISC. | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-53-13 | D04099J | = C1 | | D02191 | = C1 | | | ALL | |
| 01CX | | | JB | A | 30-11 | 34-53-13 | D04099J | = A1 | | D02191 | = A1 | | | 050-099 | |
| 01CX | | | JB | A | 31-0 | 34-53-13 | D04099J | = A1 | | D02191 | = A1 | | | 150-199, 275-299 | |
| W0335 | | 286T0335 | | | | ATC-R COAX, TOP ANT. TO DISC. | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-53-13 | D00045 | = C1 | | D04099P | = C1 | | | ALL | |
| 01CX | | | JB | A | 2-0 | 34-53-13 | D00045 | = A1 | | D04099P | = A1 | | | ALL | |
| W0337 | | 286T0337 | | | | DME-L COAX,SHELF TO ANT. DISC | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-55-11 | D04101J | = C1 | | D04103J | = C1 | | | ALL | |
| 01CX | | | JB | A | 29-1 | 34-55-11 | D04101J | = A1 | | D04103J | = A1 | | | ALL | |
| W0339 | | 286T0339 | | | | DME-L COAX,ANT. | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-55-11 | D04103P | = C1 | | D00047 | = C1 | | | ALL | |
| 01CX | | | JB | A | 2-0 | 34-55-11 | D04103P | = A1 | | D00047 | = A1 | | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0330
Page 1 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0341 | 286T0341 | | | | DME-R COAX,SHELF TO ANT. DISC | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-55-21 | D04105J | =C1 | | | D04107J | =C1 | | | ALL |
| 01CX | | | | JB | 38-0 | 34-55-21 | D04105J | =A1 | | | D04107J | =A1 | | | 050-099 |
| 01CX | | | | JB | 36-11 | 34-55-21 | D04105J | =A1 | | | D04107J | =A1 | | | 150-199, 275-299 |
| W0343 | 286T0343 | | | | DME-R COAX,ANT. | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-55-21 | D04107P | =C1 | | | D00049 | =C1 | | | ALL |
| 01CX | | | | JB | 3-0 | 34-55-21 | D04107P | =A1 | | | D00049 | =A1 | | | ALL |
| W0345 | 286T0345 | | | | ADF-L,SHELF TO ANT. DISC | | | | | | | | | | |
| 002 | 20 | | | UA | 1-6 | 34-57-11 | GD00585 | S.. | E | | D00051 | | | FA | ALL |
| 003 | 20 | | | PA | 1-6 | 34-57-11 | GD00585 | S.. | E | | D00051 | 14 | | | ALL |
| 004 | 20 | | | UA | 1-6 | 34-57-11 | D00051 | | | EA | GD00585 | S.. | E | | ALL |
| FRB | | | | | 0-0 | 34-57-11 | D04109J | | | EB | GD00711 | S.. | 2 | | ALL |
| WBK | 24 | V2 | 1C | | 59-4 | 34-57-11 | D00051 | 8 | | | D04109J | 8 | | | 050-099 |
| WBK | 24 | V2 | 1C | | 69-6 | 34-57-11 | D00051 | 8 | | | D04109J | 8 | | | 150-199, 275-299 |
| WBN | 22 | V2 | 1D | | 0-0 | 34-57-11 | D00051 | 11 | | | D04109J | 11 | | | ALL |
| WBU | 24 | V2 | 1A | | 0-0 | 34-57-11 | D00051 | 2 | | | D04109J | 2 | | | ALL |
| WGR | 24 | V2 | 1B | | 0-0 | 34-57-11 | D00051 | 5 | | | D04109J | 5 | | | ALL |
| WHT | 20 | V2 | 1E | | 0-0 | 34-57-11 | D00051 | 12 | | | D04109J | 12 | | | ALL |
| WOR | 22 | V2 | 1D | | 0-0 | 34-57-11 | D00051 | 10 | | | D04109J | 10 | | | ALL |
| WRD | 24 | V2 | 1A | | 0-0 | 34-57-11 | D00051 | 1 | | | D04109J | 1 | | | ALL |
| WRDZ | | | | 1A | 0-0 | 34-57-11 | D00051 | | | FA | D04109J | 3 | | | ALL |
| WVI | 24 | V2 | 1C | | 0-0 | 34-57-11 | D00051 | 7 | | | D04109J | 7 | | | ALL |
| WVIZ | | | | 1C | 0-0 | 34-57-11 | D00051 | | | FA | D04109J | 9 | | | ALL |
| WYL | 24 | V2 | 1B | | 0-0 | 34-57-11 | D00051 | 4 | | | D04109J | 4 | | | ALL |
| WYLZ | | | | 1B | 0-0 | 34-57-11 | D00051 | | | FA | D04109J | 6 | | | ALL |
| YAA | | | | 1F | 0-0 | 34-57-11 | D00051 | | | EA | D04109J | | | EB | ALL |
| W0349 | 286T0349 | | | | ADF-R ANTENNA | | | | | | | | | | |
| 002 | 20 | | | UA | 1-6 | 34-57-21 | GD00611 | S.. | E | | D01415 | REF | | IA | ALL |
| 003 | 20 | | | PA | 1-6 | 34-57-21 | GD00611 | S.. | E | | D01415 | 14 | | | ALL |
| 004 | 20 | | | UA | 1-6 | 34-57-21 | GD00611 | S.. | E | | D01415 | | | EA | ALL |
| FRB | | | | | 0-0 | 34-57-21 | D04113J | | | EB | GD00711 | S.. | 2 | | ALL |
| WBK | 24 | V2 | 1C | | 62-9 | 34-57-21 | D04113J | 8 | | | D01415 | 8 | | | 050-099 |
| WBK | 24 | V2 | 1C | | 73-2 | 34-57-21 | D04113J | 8 | | | D01415 | 8 | | | 150-199, 275-299 |
| WBN | 22 | V2 | 1D | | 0-0 | 34-57-21 | D04113J | 11 | | | D01415 | 11 | | | ALL |
| WBU | 24 | V2 | 1A | | 0-0 | 34-57-21 | D04113J | 2 | | | D01415 | 2 | | | ALL |
| WGR | 24 | V2 | 1B | | 0-0 | 34-57-21 | D04113J | 5 | | | D01415 | 5 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0340
Page 1
Mar 14/2007



| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|----------------------------------|----------|---------|-------|------|------|--------|--------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0349 | 286T0349 | | | ADF-R ANTENNA (continued) | | | | | | | | | | | |
| WHT | 20 | V2 | 1E | 0-0 | 34-57-21 | D04113J | | 12 | | | D01415 | 12 | | | ALL |
| WOR | 22 | V2 | 1D | 0-0 | 34-57-21 | D04113J | | 10 | | | D01415 | 10 | | | ALL |
| WRD | 24 | V2 | 1A | 0-0 | 34-57-21 | D04113J | | 1 | | | D01415 | 1 | | | ALL |
| WRDZ | | | 1A | 0-0 | 34-57-21 | D04113J | | 3 | | | D01415 | REF | IA | | ALL |
| WVI | 24 | V2 | 1C | 0-0 | 34-57-21 | D04113J | | 7 | | | D01415 | 7 | | | ALL |
| WVIZ | | | 1C | 0-0 | 34-57-21 | D04113J | | 9 | | | D01415 | REF | IA | | ALL |
| WYL | 24 | V2 | 1B | 0-0 | 34-57-21 | D04113J | | 4 | | | D01415 | 4 | | | ALL |
| WYLZ | | | 1B | 0-0 | 34-57-21 | D04113J | | 6 | | | D01415 | REF | IA | | ALL |
| YAA | | | 1F | 0-0 | 34-57-21 | D04113J | | | | EB | D01415 | | EA | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number GA CO TY | | | Description Fam FT-IN Diagram | | | From Equip Term Type Splice | | | | To Equip Term Type Splice Effectivity | | | | | |
|------------------------|-------------------------|----|----|--|----------|---------|--------------------------------|-----|---|--|--|---------|-----|----|--|------------------------------|
| W0352 | 286T0352 | | | L. STRUT-L2A-ENG INSTR, ASSY OF | | | | | | | | | | | | |
| 001 | 18 | HL | | 12-1 | SPARE | D04202P | | 1 | | | | D11354 | CAP | Y | | 050-099, 150-166, 275-277 |
| 002 | 18 | HP | AB | 12-0 | 73-34-11 | D04202P | | 2 | | | | D04232J | | 2 | | 050-099, 150-199, 275-278 |
| 002Z | | | AB | 0-0 | 73-34-11 | D04202P | | =CC | M | | | D04232J | =CC | M | | 050-099, 150-199, 275-278 |
| 003 | 18 | HL | | 12-0 | 36-11-61 | D04202P | | 3 | | | | D04232J | | 3 | | 050-099, 150-199, 275-278 |
| 004 | 18 | HL | | 12-0 | 36-11-61 | D04202P | | 4 | | | | D04232J | | 5 | | 050-099, 150-199, 275-278 |
| 006 | 18 | HL | | 12-0 | SPARE | D04202P | | 7 | | | | D04232J | | 13 | | 050-099, 150-199, 275-278 |
| 007 | 18 | HL | | 12-0 | SPARE | D04202P | | 8 | | | | D04232J | | 14 | | 050-099, 150-199, 275-278 |
| 008 | 18 | HL | | 7-2 | 36-11-61 | SP03034 | | | 8 | | | D04232J | | 4 | | 050-099, 150-199, 275-278 |
| 009 | 18 | HL | | 12-0 | 29-11-11 | D04202P | | 9 | | | | D04232J | | 9 | | 050-099, 150-199, 275-278 |
| 012 | 18 | HL | | 12-0 | 74-31-11 | D04202P | | 12 | | | | D04232J | | 12 | | 050-099, 150-199, 275-278 |
| 013 | 18 | HL | | 2-11 | 78-34-11 | GD05212 | | S.. | N | | | D11354 | | 4 | | 050-099, 150-199, 275-278 |
| 014 | 18 | HL | | 2-4 | 78-34-11 | GD05172 | | D.. | N | | | D11354 | | 3 | | 050-099, 150-199, 275-278 |
| 020 | 18 | HL | | 7-2 | 36-11-61 | SP03032 | | | 8 | | | D04232J | | 20 | | 050-099, 150-199, 275-278 |
| 023 | 18 | HL | | 12-0 | 36-11-61 | D04202P | | 21 | | | | D04232J | | 23 | | 050-099, 150-199, 275-278 |
| 026 | 18 | HL | | 12-8 | 24-11-11 | D04342P | | 4 | | | | D04216J | | 4 | | 050-099, 150-199, 275-278 |
| 027 | 18 | HL | | 12-8 | 24-11-11 | D04342P | | 21 | | | | D04216J | | 21 | | 050-099, 150-199, 275-278 |
| 028 | 18 | HL | | 12-8 | 24-11-11 | D04342P | | 16 | | | | D04216J | | 16 | | 050-099, 150-199, 275-278 |
| 030 | 18 | HL | | 12-8 | 24-11-11 | D04342P | | 22 | | | | D04216J | | 22 | | 050-099, 150-199, 275-278 |
| 031 | 16 | HL | | 4-3 | 73-21-13 | D04232J | | 37 | | | | GD05196 | S.. | N | | 050-099, 150-199, 275-278 |

WIRE LIST
D280T132

91-21-11
Section W0350
Page 1
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0352 | 286T0352 | | | L. STRUT-L2A-ENG INSTR,ASSY OF (continued) | | | | | | | | | | | | |
| 032 | 16 | | HL | 4-0 | 73-21-13 | D04232J | | 38 | | | GD05198 | S.. | N | | 050-099, 150-199, 275-278 | |
| 040 | 18 | | HL | 12-8 | 24-11-11 | D04342P | | 27 | | | D04216J | | 27 | | 050-099, 150-199, 275-278 | |
| 041 | 18 | | HL | 12-8 | 24-11-11 | D04342P | | 28 | | | D04216J | | 28 | | 050-099, 150-199, 275-278 | |
| 051 | 18 | | HL | 12-0 | SPARE | D04232J | | 7 | | | D04202P | | 11 | | 050-099, 150-199, 275-278 | |
| 052 | 18 | | HL | 12-0 | SPARE | D04232J | | 8 | | | D04202P | | 10 | | 050-099, 150-199, 275-278 | |
| 072 | 18 | | HL | 1-2 | 78-34-11 | D04182J | | 3 | | | SM00001 | | 8 | | 050-099, 150-199, 275-278 | |
| 073 | 18 | | HL | 1-2 | 78-34-11 | D04182J | | 1 | | | SM00001 | | 8 | | 050-099, 150-199, 275-278 | |
| 074 | 18 | | HL | 2-0 | 78-34-11 | D04180J | | 3 | | | SM00002 | | 8 | | 050-099, 150-199, 275-278 | |
| 075 | 18 | | HL | 2-0 | 78-34-11 | D04180J | | 1 | | | SM00002 | | 8 | | 050-099, 150-199, 275-278 | |
| 079 | 18 | | HL | 12-0 | 36-11-61 | D04202P | | 38 | | | D04232J | | 19 | | 156-162, 166-199, 277-278 | |
| 080 | 18 | | HL | 12-0 | 36-11-61 | D04202P | | 40 | | | D04232J | | 21 | | 156-162, 166-199, 277-278 | |
| 081 | 18 | | HL | 12-0 | 36-11-61 | D04202P | | 42 | | | D04232J | | 22 | | 156-162, 166-199, 277-278 | |
| 101 | 20 | | HP | EA | 5-1 | 78-36-11 | D04180J | | 6 | | SP09571 | | 8 | | 050-099, 150-199, 275-278 | |
| 101Z | | | | EA | 0-0 | 78-36-11 | D04180J | =CC | L | | SP09571 | REF | V | | 050-099, 150-199, 275-278 | |
| 102 | 20 | | HP | EB | 3-1 | 78-36-11 | D04180J | | 7 | | D04182J | | 7 | | 050-099, 150-199, 275-278 | |
| 102Z | | | | EB | 0-0 | 78-36-11 | D04180J | =CC | L | | D04182J | =CC | L | | 050-099, 150-199, 275-278 | |
| 103 | 20 | | HP | EC | 4-1 | 78-36-11 | D04182J | | 6 | | SP09573 | | 8 | | 050-099, 150-199, 275-278 | |
| 103Z | | | | EC | 0-0 | 78-36-11 | D04182J | =CC | L | | SP09573 | REF | V | | 050-099, 150-199, 275-278 | |
| 115 | 18 | | HL | | 2-11 | 78-34-11 | GD05212 | | S.. | N | D11354 | | | FX | 050-099, 150-199, 275-278 | |

WIRE LIST

D280T132

91-21-11

Section W0350

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-------|--|---------|-------|------|------|--------|-------|---------|------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0352 | 286T0352 | | | | L. STRUT-L2A-ENG INSTR, ASSY OF (continued) | | | | | | | | | | | | |
| 116 | 18 | HP | EP | 12-1 | 78-34-11 | D04202P | | 34 | | | | D11354 | | 2 | | | 050-099, 150-199, 275-278 |
| 116Z | | | EP | 0-0 | 78-34-11 | D04202P | | =CC | M | | | D11354 | | | FX | | 050-099, 150-199, 275-278 |
| 124 | 18 | HP | EX | 16-3 | 78-34-11 | D04202P | | 6 | | | | D07170J | | 1 | | | 050-099, 150-199, 275-278 |
| 124Z | | | EX | 0-0 | 78-34-11 | D04202P | | =CC | M | * | | D07170J | =CC | L | * | | 050-099, 150-199, 275-278 |
| 125 | 18 | HP | EY | 17-0 | 78-34-11 | D04202P | | 36 | | | | D07172J | | 1 | | | 050-099, 150-199, 275-278 |
| 125Z | | | EY | 0-0 | 78-34-11 | D04202P | | =CC | M | * | | D07172J | =CC | L | * | | 050-099, 150-199, 275-278 |
| 201B | 18 | HM | B | 16-11 | 78-34-11 | D04202P | | 23 | | | | SM00002 | | 8 | | | 050-099, 150-199, 275-278 |
| 201R | 18 | HM | B | 0-0 | 78-34-11 | D04202P | | 24 | | | | D04180J | | 2 | | | 050-099, 150-199, 275-278 |
| 202B | 18 | HM | A | 15-11 | 78-34-11 | D04202P | | 25 | | | | SM00001 | | 8 | | | 050-099, 150-199, 275-278 |
| 202R | 18 | HM | A | 0-0 | 78-34-11 | D04202P | | 26 | | | | D04182J | | 2 | | | 050-099, 150-199, 275-278 |
| 206B | 18 | HQ | H | 12-8 | 24-11-11 | D04342P | | 1 | | | | D04216J | | 1 | | | 050-099, 150-199, 275-278 |
| 206R | 18 | HQ | H | 0-0 | 24-11-11 | D04342P | | 2 | | | | D04216J | | 2 | | | 050-099, 150-199, 275-278 |
| 206Z | | | H | 0-0 | 24-11-11 | D04342P | | 3 | | | | D04216J | | 3 | | | 050-099, 150-199, 275-278 |
| 207B | 18 | HQ | J | 12-8 | 24-21-11 | D04342P | | 5 | | | | D04216J | | 5 | | | 050-099, 150-199, 275-278 |
| 207R | 18 | HQ | J | 0-0 | 24-21-11 | D04342P | | 6 | | | | D04216J | | 6 | | | 050-099, 150-199, 275-278 |
| 207Z | | | J | 0-0 | 24-21-11 | D04342P | | 7 | | | | D04216J | | 7 | | | 050-099, 150-199, 275-278 |
| 208B | 18 | HM | K | 12-8 | 24-11-11 | D04342P | | 12 | | | | D04216J | | 12 | | | 050-099, 150-199, 275-278 |
| 208R | 18 | HM | K | 0-0 | 24-11-11 | D04342P | | 13 | | | | D04216J | | 13 | | | 050-099, 150-199, 275-278 |
| 209B | 18 | HM | L | 12-8 | 24-11-11 | D04342P | | 14 | | | | D04216J | | 14 | | | 050-099, 150-199, 275-278 |

WIRE LIST
D280T132

91-21-11
Section W0350
Page 3
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0352 | 286T0352 | | | L. STRUT-L2A-ENG INSTR,ASSY OF (continued) | | | | | | | | | | | | |
| 209R | 18 | HM | L | 0-0 | 24-11-11 | D04342P | | 15 | | | D04216J | | 15 | | 050-099, 150-199, 275-278 | |
| 210B | 18 | HM | C | 12-8 | SPARE | D04342P | | 26 | | | D04216J | | 26 | | 050-099, 150-199, 275-278 | |
| 210R | 18 | HM | C | 0-0 | SPARE | D04342P | | 25 | | | D04216J | | 25 | | 050-099, 150-199, 275-278 | |
| 215B | 20 | HQ | IO | 6-8 | 78-36-11 | D04180J | | 5 | | | SP09575 | | 8 | | 050-099, 150-199, 275-278 | |
| 215R | 20 | HQ | IO | 0-0 | 78-36-11 | D04180J | | 4 | | | SP09577 | | 8 | | 050-099, 150-199, 275-278 | |
| 215Z | | | IO | 0-0 | 78-36-11 | D04180J | =CC | L | | | SP09575 | REF | V | | 050-099, 150-199, 275-278 | |
| 216B | 20 | HQ | IP | 5-2 | 78-36-11 | D04182J | | 5 | | | SP09575 | | 8 | | 050-099, 150-199, 275-278 | |
| 216R | 20 | HQ | IP | 0-0 | 78-36-11 | D04182J | | 4 | | | SP09577 | | 8 | | 050-099, 150-199, 275-278 | |
| 216Z | | | IP | 0-0 | 78-36-11 | D04182J | =CC | L | | | SP09575 | REF | V | | 050-099, 150-199, 275-278 | |
| 303B | 18 | HN | M | 12-8 | 24-21-11 | D04342P | | 18 | | | D04216J | | 18 | | 050-099, 150-199, 275-278 | |
| 303R | 18 | HN | M | 0-0 | 24-21-11 | D04342P | | 19 | | | D04216J | | 19 | | 050-099, 150-199, 275-278 | |
| 303Y | 18 | HN | M | 0-0 | 24-21-11 | D04342P | | 20 | | | D04216J | | 20 | | 050-099, 150-199, 275-278 | |
| 305B | 18 | HR | ME | 12-0 | 79-32-11 | D04202P | | 15 | | | D04232J | | 18 | | 050-099, 150-199, 275-278 | |
| 305R | 18 | HR | ME | 0-0 | 79-32-11 | D04202P | | 13 | | | D04232J | | 16 | | 050-099, 150-199, 275-278 | |
| 305Y | 18 | HR | ME | 0-0 | 79-32-11 | D04202P | | 14 | | | D04232J | | 17 | | 050-099, 150-199, 275-278 | |
| 305Z | | | ME | 0-0 | 79-32-11 | D04202P | =CC | M | | | D04232J | =CC | M | | 050-099, 150-199, 275-278 | |
| 401B | 18 | HT | N | 12-8 | 24-21-11 | D04342P | | 8 | | | D04216J | | 8 | | 050-099, 150-199, 275-278 | |
| 401G | 18 | HT | N | 0-0 | 24-21-11 | D04342P | | 11 | | | D04216J | | 11 | | 050-099, 150-199, 275-278 | |
| 401R | 18 | HT | N | 0-0 | 24-21-11 | D04342P | | 9 | | | D04216J | | 9 | | 050-099, 150-199, 275-278 | |

WIRE LIST
D280T132

91-21-11
Section W0350
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0352 | 286T0352 | | | L. STRUT-L2A-ENG INSTR, ASSY OF (continued) | | | | | | | | | | | |
| 401Y | 18 | HT | N | | 0-0 | 24-21-11 | D04342P | 10 | | | D04216J | 10 | | | 050-099, 150-199, 275-278 |
| W0356 | 286T0356 | | | L. STRUT-L2B-ENG INSTR | | | | | | | | | | | |
| 001 | 18 | HL | | | 11-11 | 36-11-61 | D04212P | 1 | | | D04208J | 1 | | | ALL |
| 002 | 18 | HL | | | 11-11 | 36-11-61 | D04212P | 2 | | | D04208J | 2 | | | ALL |
| 003 | 18 | HL | | | 11-11 | 36-11-61 | D04212P | 3 | | | D04208J | 3 | | | ALL |
| 004 | 18 | HL | | | 7-4 | 36-11-61 | SP03034 | | 8 | | D04208J | 4 | | | ALL |
| 005 | 18 | HL | | | 11-11 | 36-11-61 | D04212P | 5 | | | D04208J | 5 | | | ALL |
| 006 | 18 | HL | | | 11-11 | 36-11-61 | D04212P | 6 | | | D04208J | 6 | | | ALL |
| 007 | 18 | HL | | | 11-11 | 36-11-61 | D04212P | 7 | | | D04208J | 7 | | | ALL |
| 009 | 18 | HL | | | 7-4 | 36-11-61 | SP03032 | | 8 | | D04208J | 9 | | | ALL |
| 010 | 18 | HL | | | 11-11 | 36-11-61 | D04212P | 10 | | | D04208J | 10 | | | ALL |
| 011 | 18 | HL | | | 11-11 | 36-11-61 | D04212P | 11 | | | D04208J | 11 | | | ALL |
| 016 | 18 | HP | AP | | 11-11 | 79-35-11 | D04212P | 16 | | | D04208J | 16 | | | ALL |
| 016Z | | | AP | | 0-0 | 79-35-11 | D04212P | =CC | M | | D04208J | =CC | M | | ALL |
| 033 | 18 | HP | BH | | 16-7 | 75-23-11 | D04214P | 5 | | | D04192J | 5 | | | ALL |
| 033Z | | | BH | | 0-0 | 75-23-11 | D04214P | =CC | M | | D04192J | =CC | M | | ALL |
| 034 | 18 | HP | BI | | 16-7 | 75-23-11 | D04214P | 6 | | | D04192J | 6 | | | ALL |
| 034Z | | | BI | | 0-0 | 75-23-11 | D04214P | =CC | M | | D04192J | =CC | M | | ALL |
| 039 | 18 | HL | | | 11-11 | 74-31-11 | D04212P | 15 | | | D04208J | 15 | | | ALL |
| 044 | 18 | HL | | | 11-9 | SPARE | D04206P | 21 | | | D04156J | 9 | | | ALL |
| 046 | 18 | HL | | | 10-10 | 36-22-11 | D04206P | 1 | | | D11352 | 1 | | | ALL |
| 047 | 18 | HL | | | 1-9 | 36-22-11 | GD05422 | D.. | N | | D11352 | 2 | | | ALL |
| 048 | 18 | HP | BW | | 11-11 | 79-33-11 | D04212P | 22 | | | D04208J | 22 | | | ALL |
| 048Z | | | BW | | 0-0 | 79-33-11 | D04212P | =CC | M | | D04208J | =CC | M | | ALL |
| 049 | 18 | HL | | | 16-7 | SPARE | D04214P | 15 | | | D04192J | 4 | | | ALL |
| 057 | 18 | HL | | | 6-6 | 36-11-51 | GD05422 | D.. | N | | SP03034 | | 8 | | ALL |
| 058 | 18 | HL | | | 9-3 | 30-21-11 | D04212P | 25 | | | D02670 | 1 | | | ALL |
| 061 | 18 | HL | | | 10-10 | 36-11-51 | D04206P | 2 | | | D00022 | 1 | | | ALL |
| 062 | 18 | HL | | | 10-10 | 36-11-51 | D04206P | 3 | | | D00022 | 3 | | | ALL |
| 063 | 18 | HL | | | 10-10 | 36-11-51 | D04206P | 4 | | | D00022 | 5 | | | ALL |
| 064 | 18 | HL | | | 6-2 | 36-11-51 | SP03034 | | 8 | | D00022 | 6 | | | ALL |
| 065 | 18 | HL | | | 10-10 | 36-11-51 | D04206P | 6 | | | D00022 | 7 | | | ALL |
| 066 | 18 | HL | | | 10-10 | 36-11-51 | D04206P | 7 | | | D00022 | 8 | | | ALL |
| 067 | 18 | HL | | | 10-10 | 36-11-51 | D04206P | 8 | | | D00022 | 10 | | | ALL |
| 068 | 18 | HL | | | 3-9 | 36-11-51 | SM00001 | | 8 | | D00022 | 2 | | | ALL |
| 069 | 18 | HL | | | 3-9 | 36-11-51 | SM00001 | | 8 | | D00022 | 4 | | | ALL |
| 070 | 18 | HL | | | 3-9 | 36-11-51 | SM00001 | | 8 | | D00022 | 9 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0350

Page 5

Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0356 | 286T0356 | | | L. STRUT-L2B-ENG INSTR (continued) | | | | | | | | | | | | | |
| 071 | 18 | | HL | 3-9 | 36-11-51 | SM00001 | | | | 8 | | | D00022 | 11 | | | ALL |
| 072 | 18 | | HL | 4-3 | 36-23-11 | SP03032 | | | | 8 | | | D00030 | 2 | | | ALL |
| 073 | 18 | | HL | 4-3 | 36-23-11 | SP03032 | | | | 8 | | | D00030 | 4 | | | ALL |
| 074 | 18 | | HL | 7-7 | 36-23-11 | D04206P | | | 9 | | | | SM00001 | | 8 | | ALL |
| 075 | 18 | | HL | 4-6 | 36-11-51 | GD05200 | | S.. | N | | | | D00022 | 12 | | | ALL |
| 079 | 18 | | HL | 9-5 | 36-23-11 | D04206P | | | 11 | | | | D00030 | 1 | | | ALL |
| 083 | 18 | | HL | 9-5 | 36-23-11 | D04206P | | | 12 | | | | D00030 | 3 | | | ALL |
| 084 | 18 | | HL | 2-5 | 36-23-11 | GD05200 | | S.. | N | | | | D00030 | 8 | | | ALL |
| 085 | 18 | | HL | 11-9 | 36-23-11 | D04206P | | | 18 | | | | D04156J | 1 | | | ALL |
| 086 | 18 | | HL | 7-1 | 36-23-11 | SP03032 | | | | 8 | | | D04156J | 2 | | | ALL |
| 087 | 18 | | HL | 11-9 | 36-23-11 | D04206P | | | 17 | | | | D04156J | 3 | | | ALL |
| 090 | 18 | | HL | 1-11 | 30-21-11 | GD05170 | | D.. | N | | | | D02670 | 4 | | | ALL |
| 093 | 18 | | HL | 1-11 | 30-21-11 | GD05170 | | D.. | N | | | | D02670 | 2 | | | ALL |
| 094 | 18 | | HL | 2-5 | 30-21-11 | GD05200 | | S.. | N | | | | D02670 | 6 | | | ALL |
| 095 | 18 | | HL | 2-5 | 36-23-11 | SP03032 | | | | 8 | | | SM00001 | | 8 | | ALL |
| 096 | 18 | | HP | 8-2 | 75-23-11 | D04192J | | | 7 | | | | D03072 | A | | | ALL |
| 096Z | | | DU | 0-0 | 75-23-11 | D04192J | | =CC | M | | | | GD05440 | S.. | N | | ALL |
| 098 | 18 | | HL | 3-4 | 75-23-11 | GD05172 | | D.. | N | | | | D03072 | B | | | ALL |
| 100 | 18 | | HL | 8-10 | 30-21-11 | D04212P | | | 4 | | | | D00758 | 1 | | | ALL |
| 101 | 18 | | HL | 5-5 | 30-21-11 | GD05170 | | D.. | N | | | | D00758 | 2 | | | ALL |
| 102 | 16 | | HL | 4-5 | 73-21-13 | D04208J | | | 8 | | | | GD05206 | S.. | N | | ALL |
| 103 | 16 | | HL | 4-2 | 73-21-13 | D04208J | | | 20 | | | | GD05208 | S.. | N | | ALL |
| 104 | 18 | | HL | 9-3 | 30-21-11 | D04212P | | | 23 | | | | D02670 | 5 | | | ALL |
| 105 | 18 | | HL | 9-3 | 30-21-11 | D04212P | | | 24 | | | | D02670 | 3 | | | ALL |
| 107 | 18 | | HL | 3-9 | 75-23-11 | D04192J | | | 9 | | | | GD05192 | S.. | N | | ALL |
| 108 | 18 | | HL | 3-6 | 75-23-11 | D04192J | | | 10 | | | | GD05166 | D.. | N | | ALL |
| 110 | 18 | | HP | 16-7 | 75-23-11 | D04214P | | | 7 | | | | D04192J | 8 | | | ALL |
| 110Z | | | EJ | 0-0 | 75-23-11 | D04214P | | =CC | M | | | | D04192J | =CC | M | | ALL |
| 111 | 18 | | HP | 10-9 | 75-23-11 | D04214P | | | 8 | | | | D03072 | C | | | ALL |
| 111Z | | | EK | 0-0 | 75-23-11 | D04214P | | =CC | M | | | | GD05440 | S.. | N | | ALL |
| 112 | 18 | | HL | 11-11 | 36-11-61 | D04212P | | | 8 | | | | D04208J | 29 | | | ALL |
| 113 | 18 | | HL | 11-11 | 36-11-61 | D04212P | | | 9 | | | | D04208J | 30 | | | ALL |
| 116 | 18 | | HL | 7-1 | 36-11-61 | D04212P | | | 20 | | | | SP03032 | | 8 | | ALL |
| 117 | 18 | | HL | 2-0 | 36-22-21 | D01840 | | | C | | | | SM00010 | | 8 | | ALL |
| 118 | 18 | | HL | 2-0 | 36-22-21 | SM00010 | | | | 8 | | | GD05422 | D.. | N | | ALL |
| 143 | 18 | | HL | 0-6 | 78-36-11 | D04192J | | | 1 | | | | SM00004 | | 8 | | ALL |
| 144 | 18 | | HL | 0-6 | 78-36-11 | D04192J | | | 2 | | | | SM00005 | | 8 | | ALL |
| 145 | 18 | | HL | 0-6 | 78-36-11 | D04192J | | | 11 | | | | SM00004 | | 8 | | ALL |
| 146 | 18 | | HL | 1-0 | 78-36-11 | D04194J | | | 8 | | | | SM00006 | | 8 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0350

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0356 | 286T0356 | | | L. STRUT-L2B-ENG INSTR (continued) | | | | | | | | | | | |
| 147 | 18 | | HL | | 1-0 | 78-36-11 | D04194J | | | | SM00007 | | | 8 | ALL |
| 148 | 18 | | HL | | 1-0 | 78-36-11 | D04194J | | | | SM00006 | | | 8 | ALL |
| 149 | 20 | | HP | FX | 6-0 | 78-36-11 | D04192J | | | | SP09579 | | | 8 | ALL |
| 149Z | | | | FX | 0-0 | 78-36-11 | D04192J | =CC | M | | SP09579 | REF | V | | ALL |
| 150 | 20 | | HP | FY | 3-0 | 78-36-11 | D04192J | | | | D04194J | | | 10 | ALL |
| 150Z | | | | FY | 0-0 | 78-36-11 | D04192J | =CC | M | | D04194J | =CC | L | | 050-099, 150-199 |
| 150Z | | | | FY | 0-0 | 78-36-11 | D04192J | =CC | M | | D04194J | =CC | M | | 275-299 |
| 151 | 20 | | HP | GA | 4-6 | 78-36-11 | D04194J | | | | SP09581 | | | 8 | ALL |
| 151Z | | | | GA | 0-0 | 78-36-11 | D04194J | =CC | L | | SP09581 | REF | V | | 050-099, 150-199 |
| 151Z | | | | GA | 0-0 | 78-36-11 | D04194J | =CC | M | | SP09581 | REF | V | | 275-299 |
| 152 | 18 | | HL | | 0-6 | 78-36-11 | D04192J | | | | SM00005 | | | 8 | ALL |
| 153 | 18 | | HL | | 1-0 | 78-36-11 | D04194J | | | | SM00007 | | | 8 | ALL |
| 157 | 20 | | HP | GG | 16-5 | 30-21-11 | D04212P | | | | D11440 | | | 3 | ALL |
| 157Z | | | | GG | 0-0 | 30-21-11 | D04212P | =CC | M | | D11440 | =CC | L | | ALL |
| 159 | 18 | | HL | | 3-5 | 30-21-11 | D11440 | | | | GD05166 | D.. | N | | ALL |
| 163 | 20 | | HP | GM | 13-8 | 78-36-11 | D04214P | | | | SP03340 | | | 8 | ALL |
| 163Z | | | | GM | 0-0 | 78-36-11 | D04214P | =CC | M | | SP03340 | REF | V | | ALL |
| 201B | 18 | | HM | IE | 11-8 | 36-22-21 | D04206P | | | | SM00010 | | | 8 | ALL |
| 201R | 18 | | HM | IE | 0-0 | 36-22-21 | D04206P | | | | D01840 | A | | | ALL |
| 204B | 18 | | HM | D | 15-7 | 78-36-11 | D04214P | | | | SM00007 | | | 8 | ALL |
| 204R | 18 | | HM | D | 0-0 | 78-36-11 | D04214P | | | | D04194J | | | 5 | ALL |
| 205B | 18 | | HM | E | 15-7 | 78-36-11 | D04214P | | | | SM00006 | | | 8 | ALL |
| 205R | 18 | | HM | E | 0-0 | 78-36-11 | D04214P | | | | D04194J | | | 7 | ALL |
| 206B | 18 | | HM | F | 16-7 | 78-36-11 | D04214P | | | | SM00004 | | | 8 | ALL |
| 206R | 18 | | HM | F | 0-0 | 78-36-11 | D04214P | | | | D04192J | | | 12 | ALL |
| 207B | 18 | | HM | G | 16-7 | 78-36-11 | D04214P | | | | SM00005 | | | 8 | ALL |
| 207R | 18 | | HM | G | 0-0 | 78-36-11 | D04214P | | | | D04192J | | | 14 | ALL |
| 215B | 20 | | HQ | IO | 6-5 | 78-36-11 | D04192J | | | | SP09583 | | | 8 | ALL |
| 215R | 20 | | HQ | IO | 0-0 | 78-36-11 | D04192J | | | | SP09585 | | | 8 | ALL |
| 215Z | | | | IO | 0-0 | 78-36-11 | D04192J | =CC | M | | SP09583 | REF | V | | ALL |
| 216B | 20 | | HQ | IP | 4-11 | 78-36-11 | D04194J | | | | SP09583 | | | 8 | ALL |
| 216R | 20 | | HQ | IP | 0-0 | 78-36-11 | D04194J | | | | SP09585 | | | 8 | ALL |
| 216Z | | | | IP | 0-0 | 78-36-11 | D04194J | =CC | L | | SP09583 | REF | V | | 050-099, 150-199 |
| 216Z | | | | IP | 0-0 | 78-36-11 | D04194J | =CC | M | | SP09583 | REF | V | | 275-299 |
| 301B | 20 | | HR | J | 9-5 | 36-23-11 | D04206P | | | | D00030 | | | 5 | ALL |
| 301R | 20 | | HR | J | 0-0 | 36-23-11 | D04206P | | | | D00030 | | | 6 | ALL |
| 301Y | 20 | | HR | J | 0-0 | 36-23-11 | D04206P | | | | D00030 | | | 7 | ALL |
| 301Z | | | | J | 0-0 | 36-23-11 | D04206P | | | | D00030 | DED | | | ALL |
| 302B | 18 | | HR | MB | 11-11 | 73-31-11 | D04212P | | | | D04208J | | | 18 | ALL |

WIRE LIST
D280T132

91-21-11
Section W0350
Page 7
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0356 | 286T0356 | | | L. STRUT-L2B-ENG INSTR (continued) | | | | | | | | | | | | |
| 302R | 18 | HR | MB | 0-0 | 73-31-11 | D04212P | 17 | | | | D04208J | 17 | | | ALL | |
| 302Y | 18 | HR | MB | 0-0 | 73-31-11 | D04212P | 19 | | | | D04208J | 19 | | | ALL | |
| 302Z | | | MB | 0-0 | 73-31-11 | D04212P | =CC | M | | | D04208J | =CC | M | | ALL | |
| 304B | 18 | HR | MD | 11-11 | 73-33-11 | D04208J | 25 | | | | D04212P | 29 | | | 050-099, 150-199, 277-299 | |
| 304B | 18 | HR | MD | 11-11 | MULTI | D04208J | 25 | | | | D04212P | 29 | | | 275-276 | |
| 304R | 18 | HR | MD | 0-0 | 73-33-11 | D04208J | 23 | | | | D04212P | 27 | | | 050-099, 150-199, 277-299 | |
| 304R | 18 | HR | MD | 0-0 | MULTI | D04208J | 23 | | | | D04212P | 27 | | | 275-276 | |
| 304Y | 18 | HR | MD | 0-0 | 73-33-11 | D04208J | 24 | | | | D04212P | 28 | | | 050-099, 150-199, 277-299 | |
| 304Y | 18 | HR | MD | 0-0 | MULTI | D04208J | 24 | | | | D04212P | 28 | | | 275-276 | |
| 304Z | | | MD | 0-0 | 00-000 | D04208J | =CC | M | | | D04212P | =CC | M | | 050-099, 150-199, 277-299 | |
| 304Z | | | MD | 0-0 | MULTI | D04208J | =CC | M | | | D04212P | =CC | M | | 275-276 | |
| 306B | 18 | HR | MF | 11-11 | 79-31-11 | D04212P | 12 | | | | D04208J | 12 | | | ALL | |
| 306R | 18 | HR | MF | 0-0 | 79-31-11 | D04212P | 14 | | | | D04208J | 14 | | | ALL | |
| 306Y | 18 | HR | MF | 0-0 | 79-31-11 | D04212P | 13 | | | | D04208J | 13 | | | ALL | |
| 306Z | | | MF | 0-0 | 79-31-11 | D04212P | =CC | M | | | D04208J | =CC | M | | ALL | |
| 400R | 18 | 9P | | 9-2 | 26-18-12 | D04214P | 14 | | | | TS0236 | =1 | D1 | * | ALL | |
| 451R | 18 | 9P | | 9-6 | 26-18-12 | D04214P | 21 | | | | TS0237 | =1 | D1 | * | ALL | |
| 453R | 18 | 9P | | 3-8 | 26-18-12 | TS0236 | =1 | D1 | * | | TS0237 | =1 | D1 | * | ALL | |
| 454R | 18 | 9P | | 3-11 | 26-18-12 | TS0236 | =2 | D1 | | | GD05184 | D.. | E1 | | ALL | |
| 455R | 18 | 9P | | 1-4 | 26-18-12 | TS0237 | =2 | D1 | | | GD05184 | D.. | E1 | | ALL | |
| 459R | 18 | 9P | | 8-3 | 26-18-11 | D10586 | =1 | | | | D04206P | 24 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0350

Page 8 End

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|-----------------------------------|-------|----------|-------------|------|------|-----------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0360 | 286T0360 | | | L STRUT-S2B-FIRE DETECTION | | | | | | | | | | | |
| 451R | 16 | | 9P | | 9-10 | 26-11-12 | D04218P | | | 1 | D04228J | | | 1 | ALL |
| 452R | 16 | | 9P | | 9-10 | 26-11-11 | D04218P | | | 2 | D04228J | | | 2 | ALL |
| 453R | 16 | | 9P | | 9-10 | SPARE | D04218P | | | 3 | D04228J | | | 3 | ALL |
| 454R | 16 | | 9P | | 10-0 | 26-11-12 | D04218P | | | 4 | D04154J | | | 1 | ALL |
| 455R | 16 | | 9P | | 10-0 | 26-11-11 | D04218P | | | 5 | D04154J | | | 2 | ALL |
| 456R | 16 | | 9P | | 10-0 | 26-11-11 | D04218P | | | 6 | D04154J | | | 3 | ALL |
| 457R | 16 | | 9P | | 10-0 | 26-11-12 | D04218P | | | 7 | D04154J | | | 4 | ALL |

WIRE LIST
D280T132

91-21-11
Section W0360
Page 1 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|-------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0372 | 286T0372 | | | . STRUT-L2-EEC,ASSY OF | | | | | | | | | | | |
| 002 | 16 | HP | A | A | 14-0 | 73-21-20 | D04234P | 13 | | | D04224J | 13 | | | ALL |
| 002Z | | | A | A | 0-0 | 73-21-20 | D04234P | =CC | M | | D04224J | =CC | M | | ALL |
| 003 | 16 | HP | AC | AC | 11-0 | 73-21-11 | D04234P | 4 | | | SP03096 | 8 | | | ALL |
| 003Z | | | AC | AC | 0-0 | 73-21-11 | D04234P | =CC | M | | SP03096 | REF | V | | ALL |
| 006 | 20 | HP | F | F | 6-0 | 73-21-11 | D04224J | 8 | | | SP03080 | 8 | | | ALL |
| 006Z | | | F | F | 0-0 | 73-21-11 | D04224J | =CC | M | | SP03080 | REF | V | | ALL |
| 010 | 16 | HP | AA | AA | 6-0 | 73-21-11 | SP03096 | 8 | | | D04224J | 4 | | | ALL |
| 010Z | | | AA | AA | 0-0 | 73-21-11 | SP03096 | REF | V | | D04224J | =CC | M | | ALL |
| 014 | 20 | HP | AN | AN | 11-0 | 73-21-11 | D04234P | 8 | | | SP03080 | 8 | | | ALL |
| 014Z | | | AN | AN | 0-0 | 73-21-11 | D04234P | =CC | M | | SP03080 | REF | V | | ALL |
| 022 | 20 | HP | AD | AD | 4-0 | 73-21-14 | D04224J | 41 | | | SM00012 | VH | | | 050-099, 153 |
| 022 | 18 | HL | HL | HL | 1-0 | 73-21-14 | D04224J | 12 | | | D04224J | 1 | | | 150-152, 154-199, 275-299 |
| 022Z | | | AD | AD | 0-0 | 73-21-14 | D04224J | =CC | M | | SM00012 | REF | VH | | 050-099 |
| 022Z | | | AD | AD | 0-0 | 73-21-14 | D04224J | =CC | M | | SM00012 | VH | | | 153 |
| 025 | 16 | HP | J | J | 14-0 | SPARE | D04234P | 37 | | | D04224J | 37 | | | ALL |
| 025Z | | | J | J | 0-0 | SPARE | D04234P | =CC | M | | D04224J | =CC | M | | ALL |
| 040 | 20 | HP | Y | Y | 6-0 | 73-21-11 | SP03076 | 8 | | | D04224J | 7 | | | ALL |
| 040Z | | | Y | Y | 0-0 | 73-21-11 | SP03076 | REF | V | | D04224J | =CC | M | | ALL |
| 041 | 20 | HP | BP | BP | 11-0 | 73-21-11 | D04234P | 7 | | | SP03076 | 8 | | | ALL |
| 041Z | | | BP | BP | 0-0 | 73-21-11 | D04234P | =CC | M | | SP03076 | REF | V | | ALL |
| 101 | 20 | HP | EA | EA | 6-0 | 78-36-11 | D04224J | 34 | | | SP09571 | 8 | | | ALL |
| 101Z | | | EA | EA | 0-0 | 78-36-11 | D04224J | =CC | M | | SP09571 | REF | V | | ALL |
| 102 | 20 | HP | EB | EB | 6-0 | 78-36-11 | D04224J | 31 | | | SP09573 | 8 | | | ALL |
| 102Z | | | EB | EB | 0-0 | 78-36-11 | D04224J | =CC | M | | SP09573 | REF | V | | ALL |
| 107 | 20 | HP | EG | EG | 6-0 | 73-21-14 | D04224J | 11 | | | SP03124 | 8 | | | ALL |
| 107Z | | | EG | EG | 0-0 | 73-21-14 | D04224J | =CC | M | | SP03124 | REF | V | | ALL |
| 108 | 20 | HP | P | P | 11-0 | 73-21-19 | D04234P | 40 | | | SP03092 | 8 | | | ALL |
| 108Z | | | P | P | 0-0 | 73-21-19 | D04234P | =CC | M | | SP03092 | REF | V | | ALL |
| 109 | 20 | HP | H | H | 6-0 | 73-21-19 | SP03092 | 8 | | | D04224J | 18 | | | ALL |
| 109Z | | | H | H | 0-0 | 73-21-19 | SP03092 | REF | V | | D04224J | =CC | M | | ALL |
| 111 | 20 | HP | AB | AB | 11-0 | 73-21-17 | D04234P | 1 | | | SP03478 | 8 | | | ALL |
| 111Z | | | AB | AB | 0-0 | 73-21-17 | D04234P | =CC | M | | SP03478 | REF | V | | ALL |
| 112 | 20 | HP | EF | EF | 5-0 | 73-21-17 | D04224J | 42 | | | SP03478 | 8 | | | ALL |
| 112Z | | | EF | EF | 0-0 | 73-21-17 | D04224J | =CC | M | | SP03478 | REF | V | | ALL |
| 123 | 20 | HP | EW | EW | 6-0 | 78-36-11 | SP03340 | 8 | | | D04224J | 19 | | | ALL |
| 123Z | | | EW | EW | 0-0 | 78-36-11 | SP03340 | REF | V | | D04224J | =CC | M | | ALL |
| 201B | 20 | HQ | IA | IA | 14-0 | 77-12-12 | D04234P | 3 | | | D04224J | 3 | | | ALL |
| 201R | 20 | HQ | IA | IA | 0-0 | 77-12-12 | D04234P | 2 | | | D04224J | 2 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0370

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0372 | 286T0372 | | | . STRUT-L2-EEC,ASSY OF (continued) | | | | | | | | | | | |
| 201Z | | | | IA | 0-0 | 77-12-12 | D04234P | =CC | M | | D04224J | =CC | M | | ALL |
| 202B | 20 | HQ | S | | 14-0 | 73-21-13 | D04234P | 15 | | | D04224J | 15 | | | ALL |
| 202R | 20 | HQ | S | | 0-0 | 73-21-13 | D04234P | 16 | | | D04224J | 16 | | | ALL |
| 202Z | | | S | | 0-0 | 73-21-13 | D04234P | =CC | M | | D04224J | =CC | M | | ALL |
| 203B | 20 | HQ | T | | 6-0 | 73-21-14 | SP03090 | 8 | | | D04224J | 6 | | | ALL |
| 203R | 20 | HQ | T | | 0-0 | 73-21-14 | SP03086 | 8 | | | D04224J | 5 | | | ALL |
| 203Z | | | T | | 0-0 | 73-21-14 | SP03086 | REF | V | | D04224J | =CC | M | | ALL |
| 204B | 20 | HQ | U | | 14-0 | 73-21-14 | D04234P | 23 | | | D04224J | 24 | | | ALL |
| 204R | 20 | HQ | U | | 0-0 | 73-21-14 | D04234P | 24 | | | D04224J | 23 | | | ALL |
| 204Z | | | U | | 0-0 | 73-21-14 | D04234P | =CC | M | | D04224J | =CC | M | | ALL |
| 207B | 20 | HQ | IG | | 14-0 | SPARE | D04234P | 36 | | | D04224J | 36 | | | 050-099, 150-199, 275-276, 278-299 |
| 207B | 20 | HQ | IG | | 14-0 | 31-35-14 | D04234P | 36 | | | D08320J | 11 | | | 277 |
| 207R | 20 | HQ | IG | | 0-0 | SPARE | D04234P | 35 | | | D04224J | 35 | | | 050-099, 150-199, 275-276, 278-299 |
| 207R | 20 | HQ | IG | | 0-0 | 31-35-14 | D04234P | 35 | | | D08320J | 10 | | | 277 |
| 207Z | | | IG | | 0-0 | SPARE | D04234P | =CC | M | | D04224J | =CC | M | | 050-099, 150-199, 275-276, 278-299 |
| 207Z | | | IG | | 0-0 | 31-35-14 | D04234P | =CC | M | | D08320J | =CC | M | | 277 |
| 210B | 20 | HQ | K | | 6-0 | 73-21-14 | SP03082 | 8 | | | D04224J | 33 | | | ALL |
| 210R | 20 | HQ | K | | 0-0 | 73-21-14 | SP03078 | 8 | | | D04224J | 32 | | | ALL |
| 210Z | | | K | | 0-0 | 73-21-14 | SP03078 | REF | V | | D04224J | =CC | M | | ALL |
| 218B | 20 | HQ | IR | | 6-0 | 78-36-11 | D04224J | 30 | | | SP09575 | 8 | | | ALL |
| 218R | 20 | HQ | IR | | 0-0 | 78-36-11 | D04224J | 29 | | | SP09577 | 8 | | | ALL |
| 218Z | | | IR | | 0-0 | 78-36-11 | D04224J | =CC | M | | SP09575 | REF | V | | ALL |
| 220B | 20 | HQ | IT | | 11-0 | 73-21-14 | D04234P | 6 | | | SP03082 | 8 | | | ALL |
| 220R | 20 | HQ | IT | | 0-0 | 73-21-14 | D04234P | 5 | | | SP03078 | 8 | | | ALL |
| 220Z | | | IT | | 0-0 | 73-21-14 | D04234P | =CC | M | | SP03078 | REF | V | | ALL |
| 226B | 20 | HQ | JA | | 6-0 | 73-21-14 | D04224J | 10 | | | SP03198 | 8 | | | ALL |
| 226R | 20 | HQ | JA | | 0-0 | 73-21-14 | D04224J | 9 | | | SP03196 | 8 | | | ALL |
| 226Z | | | JA | | 0-0 | 73-21-14 | D04224J | =CC | M | | SP03196 | REF | V | | ALL |
| 227B | 20 | HQ | JB | | 14-0 | 73-21-17 | D04234P | 28 | | | D04224J | 28 | | | ALL |
| 227R | 20 | HQ | JB | | 0-0 | 73-21-12 | D04234P | 17 | | | D04224J | 17 | | | ALL |
| 227Z | | | JB | | 0-0 | 73-21-17 | D04234P | =CC | M | | D04224J | =CC | M | | 050-099, 150-199, 275-276, 278-299 |
| 227Z | | | JB | | 0-0 | 73-21-12 | D04234P | =CC | M | | D04224J | =CC | M | | 277 |
| 230B | 20 | HQ | JC | | 4-0 | 73-21-14 | D04224J | 12 | | | SM00012 | VH | | | 050-099 |
| 230B | 20 | HQ | A0 | | 4-0 | 73-21-14 | D04224J | 12 | | | SM00012 | VH | | | 153 |
| 230R | 20 | HQ | JC | | 0-0 | 73-21-14 | D04224J | 1 | | | SM00012 | VH | | | 050-099 |

WIRE LIST
D280T132



| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0372 | 286T0372 | | | . STRUT-L2-EEC,ASSY OF (continued) | | | | | | | | | | | |
| 230R | 20 | HQ | A0 | 0-0 | 73-21-14 | D04224J | | 1 | | | SM00012 | | VH | | 153 |
| 230Z | | | JC | 0-0 | 73-21-14 | D04224J | =CC | M | | | SM00012 | REF | VH | | 050-099 |
| 230Z | | | A0 | 0-0 | 73-21-14 | D04224J | =CC | M | | | SM00012 | | VH | | 153 |
| 301B | 20 | HR | AF | 14-0 | 73-21-13 | D04234P | | 27 | | | D04224J | 27 | | | ALL |
| 301R | 20 | HR | AF | 0-0 | 73-21-13 | D04234P | | 26 | | | D04224J | 26 | | | ALL |
| 301Y | 20 | HR | AF | 0-0 | 73-21-13 | D04234P | | 25 | | | D04224J | 25 | | | ALL |
| 301Z | | | AF | 0-0 | 73-21-13 | D04234P | =CC | M | | | D04224J | =CC | M | | ALL |
| 305B | 20 | HR | ME | 14-0 | 73-21-11 | D04234P | | 10 | | | D04224J | 40 | | | ALL |
| 305R | 20 | HR | ME | 0-0 | 73-21-11 | D04234P | | 19 | | | D04224J | 39 | | | ALL |
| 305Y | 20 | HR | ME | 0-0 | 73-21-11 | D04234P | | 9 | | | D04224J | 38 | | | ALL |
| 305Z | | | ME | 0-0 | 73-21-11 | D04234P | =CC | M | | | D04224J | =CC | M | | ALL |
| W0374 | 286T0374 | | | R STRUT-R2A-ENG INSTR,ASSY OF | | | | | | | | | | | |
| 001 | 18 | HL | | 9-7 | 78-34-21 | D04242P | | 1 | | | D11438 | CAP | Y | | 050-099, 150-155, 163-165, 275-276 |
| 001 | 18 | HL | | 9-7 | SPARE | D04242P | | 1 | | | D11438 | CAP | Y | | 156-162, 166, 277 |
| 002 | 18 | HP | AB | 9-5 | 73-34-11 | D04242P | | 2 | | | D04240J | 2 | | | 050-099, 150-166, 275-299 |
| 002Z | | | AB | 0-0 | 73-34-11 | D04242P | =CC | M | | | D04240J | =CC | M | | 050-099, 150-166, 275-299 |
| 003 | 18 | HL | | 9-5 | 36-11-62 | D04242P | | 3 | | | D04240J | 3 | | | 050-099, 150-166, 275-299 |
| 004 | 18 | HL | | 9-5 | 36-11-62 | D04242P | | 4 | | | D04240J | 5 | | | 050-099, 150-166, 275-299 |
| 006 | 18 | HL | | 9-5 | SPARE | D04242P | | 7 | | | D04240J | 13 | | | 050-099, 150-166, 275-299 |
| 007 | 18 | HL | | 9-5 | SPARE | D04242P | | 8 | | | D04240J | 14 | | | 050-099, 150-166, 275-299 |
| 008 | 18 | HL | | 7-2 | 36-11-62 | SP03244 | | 8 | | | D04240J | 4 | | | 050-099, 150-166, 275-299 |
| 009 | 18 | HL | | 9-5 | 29-11-21 | D04242P | | 9 | | | D04240J | 9 | | | 050-099, 150-166, 275-299 |
| 012 | 18 | HL | | 9-5 | 74-31-21 | D04242P | | 12 | | | D04240J | 12 | | | 050-099, 150-166, 275-299 |
| 013 | 18 | HL | | 2-11 | 78-34-21 | GD05278 | S.. | N | | | D11438 | 4 | | | 050-099, 150-166, 275-299 |
| 014 | 18 | HL | | 2-4 | 78-34-21 | GD05238 | D.. | N | | | D11438 | 3 | | | 050-099, 150-166, 275-299 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0374 | 286T0374 | | | R STRUT-R2A-ENG INSTR,ASSY OF (continued) | | | | | | | | | | | | |
| 020 | 18 | | HL | 7-2 | 36-11-62 | SP03122 | | | 8 | | D04240J | 20 | | | 050-099, 150-166, 275-299 | |
| 023 | 18 | | HL | 9-5 | 36-11-62 | D04242P | | | 21 | | D04240J | 23 | | | 050-099, 150-166, 275-299 | |
| 026 | 18 | | HL | 9-3 | 24-11-21 | D04344P | | | 4 | | D04266J | 4 | | | 050-099, 150-166, 275-299 | |
| 027 | 18 | | HL | 9-3 | 24-11-21 | D04344P | | | 21 | | D04266J | 21 | | | 050-099, 150-166, 275-299 | |
| 028 | 18 | | HL | 9-3 | 24-11-21 | D04344P | | | 16 | | D04266J | 16 | | | 050-099, 150-166, 275-299 | |
| 030 | 18 | | HL | 9-3 | 24-11-21 | D04344P | | | 22 | | D04266J | 22 | | | 050-099, 150-166, 275-299 | |
| 031 | 16 | | HL | 4-4 | 73-21-13 | D04240J | | | 37 | | GD05262 | S.. | N | | 050-099, 150-166, 275-299 | |
| 032 | 16 | | HL | 3-11 | 73-21-13 | D04240J | | | 38 | | GD05264 | S.. | N | | 050-099, 150-166, 275-299 | |
| 040 | 18 | | HL | 9-3 | 24-11-21 | D04344P | | | 27 | | D04266J | 27 | | | 050-099, 150-166, 275-299 | |
| 041 | 18 | | HL | 9-3 | 24-11-21 | D04344P | | | 28 | | D04266J | 28 | | | 050-099, 150-166, 275-299 | |
| 051 | 18 | | HL | 9-5 | SPARE | D04240J | | | 7 | | D04242P | 11 | | | 050-099, 150-166, 275-299 | |
| 052 | 18 | | HL | 9-5 | SPARE | D04240J | | | 8 | | D04242P | 10 | | | 050-099, 150-166, 275-299 | |
| 072 | 18 | | HL | 1-2 | 78-34-21 | D04162J | | | 3 | | SM00001 | | 8 | | 050-099, 150-166, 275-299 | |
| 073 | 18 | | HL | 1-2 | 78-34-21 | D04162J | | | 1 | | SM00001 | | 8 | | 050-099, 150-166, 275-299 | |
| 074 | 18 | | HL | 2-0 | 78-34-21 | D04160J | | | 3 | | SM00002 | | 8 | | 050-099, 150-166, 275-299 | |
| 075 | 18 | | HL | 2-0 | 78-34-21 | D04160J | | | 1 | | SM00002 | | 8 | | 050-099, 150-166, 275-299 | |
| 079 | 18 | | HL | 9-5 | 36-11-62 | D04242P | | | 38 | | D04240J | 19 | | | 156-162, 166, 277-299 | |
| 080 | 18 | | HL | 9-5 | 36-11-62 | D04242P | | | 40 | | D04240J | 21 | | | 156-162, 166, 277-299 | |
| 081 | 18 | | HL | 9-5 | 36-11-62 | D04242P | | | 42 | | D04240J | 22 | | | 156-162, 166, 277-299 | |
| 101 | 20 | | HP | EA | 5-1 | 78-36-21 | D04160J | | 6 | | SP09587 | | 8 | | 050-099, 150-166, 275-299 | |
| 101Z | | | | EA | 0-0 | 78-36-21 | D04160J | | = CC | L | SP09587 | REF | V | | 050-099, 150-166, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W0370
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|------|--|---------|-------|------|------|--------|---------|------|------|--------|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0374 | 286T0374 | | | | R STRUT-R2A-ENG INSTR,ASSY OF (continued) | | | | | | | | | | |
| 102 | 20 | HP | EB | 3-1 | 78-36-21 | D04160J | | 7 | | | D04162J | | 7 | | 050-099, 150-166, 275-299 |
| 102Z | | | EB | 0-0 | 78-36-21 | D04160J | =CC | L | | | D04162J | =CC | L | | 050-099, 150-166, 275-299 |
| 103 | 20 | HP | EC | 4-1 | 78-36-21 | D04162J | | 6 | | | SP09589 | | 8 | | 050-099, 150-166, 275-299 |
| 103Z | | | EC | 0-0 | 78-36-21 | D04162J | =CC | L | | | SP09589 | REF | V | | 050-099, 150-166, 275-299 |
| 115 | 18 | HL | | 2-11 | 78-34-21 | GD05278 | | S.. | N | | D11438 | | | FX | 050-099, 150-166, 275-299 |
| 116 | 18 | HP | EP | 9-7 | 78-34-21 | D04242P | | 34 | | | D11438 | | 2 | | 050-099, 150-166, 275-299 |
| 116Z | | | EP | 0-0 | 78-34-21 | D04242P | =CC | M | | | D11438 | | | FX | 050-099, 150-166, 275-299 |
| 124 | 18 | HP | EX | 13-8 | 78-34-21 | D04242P | | 6 | | | D07190J | | 1 | | 050-099, 150-166, 275-299 |
| 124Z | | | EX | 0-0 | 78-34-21 | D04242P | =CC | M | * | | D07190J | =CC | L | * | 050-099, 150-166, 275-299 |
| 125 | 18 | HP | EY | 14-4 | 78-34-21 | D04242P | | 36 | | | D07192J | | 1 | | 050-099, 150-166, 275-299 |
| 125Z | | | EY | 0-0 | 78-34-21 | D04242P | =CC | M | * | | D07192J | =CC | L | * | 050-099, 150-166, 275-299 |
| 201B | 18 | HM | B | 14-4 | 78-34-21 | D04242P | | 23 | | | SM00002 | | 8 | | 050-099, 150-155, 163-165, 275-276 |
| 201B | 18 | HM | B | 14-4 | 78-34-21 | SM00002 | | | 8 | | D04242P | | 23 | | 156-162, 166, 277-299 |
| 201R | 18 | HM | B | 0-0 | 78-34-21 | D04242P | | 24 | | | D04160J | | 2 | | 050-099, 150-155, 163-165, 275-276 |
| 201R | 18 | HM | B | 0-0 | 78-34-21 | D04160J | | 2 | | | D04242P | | 24 | | 156-162, 166, 277-299 |
| 202B | 18 | HM | A | 13-4 | 78-34-21 | D04242P | | 25 | | | SM00001 | | 8 | | 050-099, 150-166, 275-299 |
| 202R | 18 | HM | A | 0-0 | 78-34-21 | D04242P | | 26 | | | D04162J | | 2 | | 050-099, 150-166, 275-299 |
| 206B | 20 | HQ | H | 9-3 | 24-11-21 | D04344P | | 1 | | | D04266J | | 1 | | 050-099, 150-166, 275-299 |
| 206R | 20 | HQ | H | 0-0 | 24-11-21 | D04344P | | 2 | | | D04266J | | 2 | | 050-099, 150-166, 275-299 |
| 206Z | | | H | 0-0 | 24-11-21 | D04344P | | 3 | | | D04266J | | 3 | | 050-099, 150-166, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0370

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0374 | 286T0374 | | | | R STRUT-R2A-ENG INSTR,ASSY OF (continued) | | | | | | | | | | | |
| 207B | 18 | HQ | J | 9-3 | 24-21-21 | D04344P | | 5 | | | D04266J | | 5 | | 050-099, 150-166, 275-299 | |
| 207R | 18 | HQ | J | 0-0 | 24-21-21 | D04344P | | 6 | | | D04266J | | 6 | | 050-099, 150-166, 275-299 | |
| 207Z | | | J | 0-0 | 24-21-21 | D04344P | | 7 | | | D04266J | | 7 | | 050-099, 150-166, 275-299 | |
| 208B | 18 | HM | K | 9-3 | 24-11-21 | D04344P | | 12 | | | D04266J | | 12 | | 050-099, 150-166, 275-299 | |
| 208R | 18 | HM | K | 0-0 | 24-11-21 | D04344P | | 13 | | | D04266J | | 13 | | 050-099, 150-166, 275-299 | |
| 209B | 18 | HM | L | 9-3 | 24-11-21 | D04344P | | 14 | | | D04266J | | 14 | | 050-099, 150-166, 275-299 | |
| 209R | 18 | HM | L | 0-0 | 24-11-21 | D04344P | | 15 | | | D04266J | | 15 | | 050-099, 150-166, 275-299 | |
| 210B | 18 | HM | C | 9-3 | SPARE | D04344P | | 26 | | | D04266J | | 26 | | 050-099, 150-166, 275-299 | |
| 210R | 18 | HM | C | 0-0 | SPARE | D04344P | | 25 | | | D04266J | | 25 | | 050-099, 150-166, 275-299 | |
| 215B | 20 | HQ | IO | 6-8 | 78-36-21 | D04160J | | 5 | | | SP09591 | | 8 | | 050-099, 150-166, 275-299 | |
| 215R | 20 | HQ | IO | 0-0 | 78-36-21 | D04160J | | 4 | | | SP09593 | | 8 | | 050-099, 150-166, 275-299 | |
| 215Z | | | IO | 0-0 | 78-36-21 | D04160J | | = CC | L | | SP09591 | REF | V | | 050-099, 150-166, 275-299 | |
| 216B | 20 | HQ | IP | 5-2 | 78-36-21 | D04162J | | 5 | | | SP09591 | | 8 | | 050-099, 150-166, 275-299 | |
| 216R | 20 | HQ | IP | 0-0 | 78-36-21 | D04162J | | 4 | | | SP09593 | | 8 | | 050-099, 150-166, 275-299 | |
| 216Z | | | IP | 0-0 | 78-36-21 | D04162J | | = CC | L | | SP09591 | REF | V | | 050-099, 150-166, 275-299 | |
| 303B | 18 | HN | M | 9-3 | 24-21-21 | D04344P | | 18 | | | D04266J | | 18 | | 050-099, 150-166, 275-299 | |
| 303R | 18 | HN | M | 0-0 | 24-21-21 | D04344P | | 19 | | | D04266J | | 19 | | 050-099, 150-166, 275-299 | |
| 303Y | 18 | HN | M | 0-0 | 24-21-21 | D04344P | | 20 | | | D04266J | | 20 | | 050-099, 150-166, 275-299 | |
| 305B | 18 | HR | ME | 9-5 | 79-32-11 | D04242P | | 15 | | | D04240J | | 18 | | 050-099, 150-166, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W0370
Page 6
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|------|--|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0374 | 286T0374 | | | | R STRUT-R2A-ENG INSTR,ASSY OF (continued) | | | | | | | | | | | |
| 305R | 18 | HR | ME | 0-0 | 79-32-11 | D04242P | | 13 | | | D04240J | | 16 | | 050-099, 150-166, 275-299 | |
| 305Y | 18 | HR | ME | 0-0 | 79-32-11 | D04242P | | 14 | | | D04240J | | 17 | | 050-099, 150-166, 275-299 | |
| 305Z | | | ME | 0-0 | 79-32-11 | D04242P | | =CC | M | | D04240J | | =CC | M | 050-099, 150-166, 275-299 | |
| 401B | 18 | HT | N | 9-3 | 24-21-21 | D04344P | | 8 | | | D04266J | | 8 | | 050-099, 150-166, 275-299 | |
| 401G | 18 | HT | N | 0-0 | 24-21-21 | D04344P | | 11 | | | D04266J | | 11 | | 050-099, 150-166, 275-299 | |
| 401R | 18 | HT | N | 0-0 | 24-21-21 | D04344P | | 9 | | | D04266J | | 9 | | 050-099, 150-166, 275-299 | |
| 401Y | 18 | HT | N | 0-0 | 24-21-21 | D04344P | | 10 | | | D04266J | | 10 | | 050-099, 150-166, 275-299 | |
| W0375 | 286T0375 | | | | MKR BCN COAX,ANT. | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-32-11 | D04071P | | =C1 | | | D00083 | | =C1 | | ALL | |
| 01CX | | | 66 | A | 2-9 | 34-32-11 | D04071P | =A1 | | | D00083 | | =A1 | | ALL | |
| W0376 | 286T0376 | | | | R. STRUT-R2B-ENG INSTR | | | | | | | | | | | |
| 001 | 18 | HL | | 10-0 | 36-11-62 | D04252P | | 1 | | | D04258J | | 1 | | ALL | |
| 002 | 18 | HL | | 10-0 | 36-11-62 | D04252P | | 2 | | | D04258J | | 2 | | ALL | |
| 003 | 18 | HL | | 10-0 | 36-11-62 | D04252P | | 3 | | | D04258J | | 3 | | ALL | |
| 004 | 18 | HL | | 7-5 | 36-11-62 | SP03244 | | | 8 | | D04258J | | 4 | | ALL | |
| 005 | 18 | HL | | 10-0 | 36-11-62 | D04252P | | 5 | | | D04258J | | 5 | | ALL | |
| 006 | 18 | HL | | 10-0 | 36-11-62 | D04252P | | 6 | | | D04258J | | 6 | | ALL | |
| 007 | 18 | HL | | 10-0 | 36-11-62 | D04252P | | 7 | | | D04258J | | 7 | | ALL | |
| 009 | 18 | HL | | 7-5 | 36-11-62 | SP03122 | | | 8 | | D04258J | | 9 | | ALL | |
| 010 | 18 | HL | | 10-0 | 36-11-62 | D04252P | | 10 | | | D04258J | | 10 | | ALL | |
| 011 | 18 | HL | | 10-0 | 36-11-62 | D04252P | | 11 | | | D04258J | | 11 | | ALL | |
| 016 | 18 | HP | AP | 10-0 | 79-35-11 | D04252P | | 16 | | | D04258J | | 16 | | ALL | |
| 016Z | | | AP | 0-0 | 79-35-11 | D04252P | | =CC | M | | D04258J | | =CC | M | ALL | |
| 033 | 18 | HP | BH | 14-7 | 75-23-11 | D04254P | | 5 | | | D04166J | | 5 | | ALL | |
| 033Z | | | BH | 0-0 | 75-23-11 | D04254P | | =CC | M | | D04166J | | =CC | M | ALL | |
| 034 | 18 | HP | BI | 14-7 | 75-23-11 | D04254P | | 6 | | | D04166J | | 6 | | ALL | |
| 034Z | | | BI | 0-0 | 75-23-11 | D04254P | | =CC | M | | D04166J | | =CC | M | ALL | |
| 039 | 18 | HL | | 10-0 | 74-31-21 | D04252P | | 15 | | | D04258J | | 15 | | ALL | |
| 044 | 18 | HL | | 9-9 | SPARE | D04248P | | 21 | | | D04150J | | 9 | | ALL | |
| 046 | 18 | HL | | 8-10 | 36-22-11 | D04248P | | 1 | | | D11436 | | 1 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0370

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0376 | 286T0376 | | | R. STRUT-R2B-ENG INSTR (continued) | | | | | | | | | | | | | |
| 047 | 18 | | HL | | 1-10 | 36-22-11 | D11436 | | 2 | | | | GD05424 | D.. | N | | ALL |
| 048 | 18 | | HP | BW | 10-0 | 79-33-11 | D04252P | | 22 | | | | D04258J | 22 | | | ALL |
| 048Z | | | | BW | 0-0 | 79-33-11 | D04252P | =CC | M | | | | D04258J | =CC | M | | ALL |
| 057 | 18 | | HL | | 6-6 | 36-11-52 | GD05424 | | D.. | N | | | SP03244 | | 8 | | ALL |
| 058 | 18 | | HL | | 7-4 | 30-21-11 | D04252P | | 25 | | | | D02760 | 1 | | | ALL |
| 061 | 18 | | HL | | 8-10 | 36-11-52 | D04248P | | 2 | | | | D00064 | 1 | | | ALL |
| 062 | 18 | | HL | | 8-10 | 36-11-52 | D04248P | | 3 | | | | D00064 | 3 | | | ALL |
| 063 | 18 | | HL | | 8-10 | 36-11-52 | D04248P | | 4 | | | | D00064 | 5 | | | ALL |
| 064 | 18 | | HL | | 6-3 | 36-11-52 | SP03244 | | | 8 | | | D00064 | 6 | | | ALL |
| 065 | 18 | | HL | | 8-10 | 36-11-52 | D04248P | | 6 | | | | D00064 | 7 | | | ALL |
| 066 | 18 | | HL | | 8-10 | 36-11-52 | D04248P | | 7 | | | | D00064 | 8 | | | ALL |
| 067 | 18 | | HL | | 8-10 | 36-11-52 | D04248P | | 8 | | | | D00064 | 10 | | | ALL |
| 068 | 18 | | HL | | 4-1 | 36-11-52 | SM00001 | | | 8 | | | D00064 | 2 | | | ALL |
| 069 | 18 | | HL | | 4-1 | 36-11-52 | SM00001 | | | 8 | | | D00064 | 4 | | | ALL |
| 070 | 18 | | HL | | 4-1 | 36-11-52 | SM00001 | | | 8 | | | D00064 | 9 | | | ALL |
| 071 | 18 | | HL | | 4-1 | 36-11-52 | SM00001 | | | 8 | | | D00064 | 11 | | | ALL |
| 072 | 18 | | HL | | 4-4 | 36-23-21 | SP03122 | | | 8 | | | D00068 | 2 | | | ALL |
| 073 | 18 | | HL | | 4-4 | 36-23-21 | SP03122 | | | 8 | | | D00068 | 4 | | | ALL |
| 074 | 18 | | HL | | 4-9 | 36-23-21 | D04248P | | | 9 | | | SM00001 | | 8 | | ALL |
| 075 | 18 | | HL | | 4-5 | 36-11-52 | GD05266 | | S.. | N | | | D00064 | 12 | | | ALL |
| 079 | 18 | | HL | | 7-5 | 36-23-21 | D04248P | | | 11 | | | D00068 | 1 | | | ALL |
| 083 | 18 | | HL | | 7-5 | 36-23-21 | D04248P | | | 12 | | | D00068 | 3 | | | ALL |
| 084 | 18 | | HL | | 2-5 | 36-23-21 | GD05266 | | S.. | N | | | D00068 | 8 | | | ALL |
| 085 | 18 | | HL | | 9-9 | 36-23-21 | D04248P | | | 18 | | | D04150J | 1 | | | ALL |
| 086 | 18 | | HL | | 7-2 | 36-23-21 | SP03122 | | | 8 | | | D04150J | 2 | | | ALL |
| 087 | 18 | | HL | | 9-9 | 36-23-21 | D04248P | | | 17 | | | D04150J | 3 | | | ALL |
| 090 | 18 | | HL | | 1-11 | 30-21-11 | GD05236 | | D.. | N | | | D02760 | 4 | | | ALL |
| 093 | 18 | | HL | | 1-11 | 30-21-11 | GD05236 | | D.. | N | | | D02760 | 2 | | | ALL |
| 094 | 18 | | HL | | 2-4 | 30-21-11 | GD05266 | | S.. | N | | | D02760 | 6 | | | ALL |
| 095 | 18 | | HL | | 2-2 | 36-23-21 | SP03122 | | | 8 | | | SM00001 | | 8 | | ALL |
| 096 | 18 | | HP | DU | 8-2 | 75-23-11 | D04166J | | | 7 | | | D03250 | A | | | ALL |
| 096Z | | | | DU | 0-0 | 75-23-11 | D04166J | =CC | M | | | | GD05442 | S.. | N | | ALL |
| 098 | 18 | | HL | | 3-4 | 75-23-11 | GD05238 | | D.. | N | | | D03250 | B | | | ALL |
| 100 | 18 | | HL | | 6-11 | 30-21-11 | D04252P | | | 4 | | | D00742 | 1 | | | ALL |
| 101 | 18 | | HL | | 6-0 | 30-21-11 | GD05236 | | D.. | N | | | D00742 | 2 | | | ALL |
| 102 | 16 | | HL | | 4-6 | 73-21-13 | D04258J | | | 8 | | | GD05272 | S.. | N | | ALL |
| 103 | 16 | | HL | | 4-3 | 73-21-13 | D04258J | | | 20 | | | GD05274 | S.. | N | | ALL |
| 104 | 18 | | HL | | 7-4 | 30-21-11 | D04252P | | | 23 | | | D02760 | 5 | | | ALL |
| 105 | 18 | | HL | | 7-4 | 30-21-11 | D04252P | | | 24 | | | D02760 | 3 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0370
Page 8
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0376 | 286T0376 | | | R. STRUT-R2B-ENG INSTR (continued) | | | | | | | | | | | | | |
| 107 | 18 | | HL | 3-9 | 75-23-11 | D04166J | | | | 9 | | | GD05258 | S.. | N | | ALL |
| 108 | 18 | | HL | 3-6 | 75-23-11 | D04166J | | | | 10 | | | GD05232 | D.. | N | | ALL |
| 110 | 18 | | HP | EJ | 14-7 | 75-23-11 | D04254P | | | 7 | | | D04166J | 8 | | | ALL |
| 110Z | | | | EJ | 0-0 | 75-23-11 | D04254P | =CC | M | | | | D04166J | =CC | M | | ALL |
| 111 | 18 | | HP | EK | 8-10 | 75-23-11 | D04254P | | | 8 | | | D03250 | C | | | ALL |
| 111Z | | | | EK | 0-0 | 75-23-11 | D04254P | =CC | M | | | | GD05442 | S.. | N | | ALL |
| 112 | 18 | | HL | | 10-0 | 36-11-62 | D04252P | | | 8 | | | D04258J | 29 | | | ALL |
| 113 | 18 | | HL | | 10-0 | 36-11-62 | D04252P | | | 9 | | | D04258J | 30 | | | ALL |
| 116 | 18 | | HL | | 4-10 | 36-11-62 | D04252P | | | 20 | | | SP03122 | | 8 | | ALL |
| 117 | 18 | | HL | | 2-0 | 36-22-21 | D01842 | | | C | | | SM00010 | | 8 | | ALL |
| 118 | 18 | | HL | | 2-0 | 36-22-21 | SM00010 | | | | 8 | | GD05424 | D.. | N | | ALL |
| 143 | 18 | | HL | | 1-0 | 78-36-21 | SM00004 | | | | 8 | | D04166J | 1 | | | ALL |
| 144 | 18 | | HL | | 1-0 | 78-36-21 | SM00005 | | | | 8 | | D04166J | 2 | | | ALL |
| 145 | 18 | | HL | | 1-0 | 78-36-21 | SM00004 | | | | 8 | | D04166J | 11 | | | ALL |
| 146 | 18 | | HL | | 0-7 | 78-36-21 | SM00006 | | | | 8 | | D04164J | 8 | | | 050-099, 150-199 |
| 146 | 18 | | HL | | 1-0 | 78-36-21 | SM00006 | | | | 8 | | D04164J | 8 | | | 275-299 |
| 147 | 18 | | HL | | 0-7 | 78-36-21 | SM00007 | | | | 8 | | D04164J | 9 | | | 050-099, 150-199 |
| 147 | 18 | | HL | | 1-0 | 78-36-21 | SM00007 | | | | 8 | | D04164J | 9 | | | 275-299 |
| 148 | 18 | | HL | | 0-7 | 78-36-21 | SM00006 | | | | 8 | | D04164J | 6 | | | 050-099, 150-199 |
| 148 | 18 | | HL | | 1-0 | 78-36-21 | SM00006 | | | | 8 | | D04164J | 6 | | | 275-299 |
| 149 | 20 | | HP | FX | 6-0 | 78-36-21 | D04166J | | | 17 | | | SP09595 | | 8 | | ALL |
| 149Z | | | | FX | 0-0 | 78-36-21 | D04166J | =CC | M | | | | SP09595 | REF | V | | ALL |
| 150 | 20 | | HP | FY | 3-0 | 78-36-21 | D04166J | | | 18 | | | D04164J | 10 | | | ALL |
| 150Z | | | | FY | 0-0 | 78-36-21 | D04166J | =CC | L | | | | D04164J | =CC | L | | 050-099, 150-199 |
| 150Z | | | | FY | 0-0 | 78-36-21 | D04166J | =CC | M | | | | D04164J | =CC | L | | 275-299 |
| 151 | 20 | | HP | GA | 4-5 | 78-36-21 | D04164J | | | 1 | | | SP09597 | | 8 | | ALL |
| 151Z | | | | GA | 0-0 | 78-36-21 | D04164J | =CC | M | | | | SP09597 | REF | V | | 050-099, 150-199 |
| 151Z | | | | GA | 0-0 | 78-36-21 | D04164J | =CC | L | | | | SP09597 | REF | V | | 275-299 |
| 152 | 18 | | HL | | 1-0 | 78-36-21 | SM00005 | | | | 8 | | D04166J | 13 | | | ALL |
| 153 | 18 | | HL | | 0-7 | 78-36-21 | SM00007 | | | | 8 | | D04164J | 4 | | | 050-099, 150-199 |
| 153 | 18 | | HL | | 1-0 | 78-36-21 | SM00007 | | | | 8 | | D04164J | 4 | | | 275-299 |
| 157 | 20 | | HP | GG | 14-6 | 30-21-11 | D04252P | | | 26 | | | D11442 | 3 | | | ALL |
| 157Z | | | | GG | 0-0 | 30-21-11 | D04252P | =CC | M | | | | D11442 | =CC | L | | ALL |
| 159 | 18 | | HL | | 3-5 | 30-21-11 | D11442 | | | 1 | | | GD05232 | D.. | N | | ALL |
| 168 | 20 | | HP | GR | 11-8 | 78-36-21 | D04254P | | | 9 | | | SP03342 | | 8 | | ALL |
| 168Z | | | | GR | 0-0 | 78-36-21 | D04254P | =CC | M | | | | SP03342 | REF | V | | ALL |
| 201B | 18 | | HM | IE | 9-7 | 36-22-21 | D04248P | | | 20 | | | SM00010 | | 8 | | ALL |
| 201R | 18 | | HM | IE | 0-0 | 36-22-21 | D04248P | | | 19 | | | D01842 | A | | | ALL |
| 204B | 18 | | HM | D | 13-7 | 78-36-21 | D04254P | | | 30 | | | SM00007 | | 8 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0370

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0376 | 286T0376 | | | R. STRUT-R2B-ENG INSTR (continued) | | | | | | | | | | | |
| 204R | 18 | HM | D | 0-0 | 78-36-21 | D04254P | 29 | | | | D04164J | 5 | | | ALL |
| 205B | 18 | HM | E | 13-7 | 78-36-21 | D04254P | 23 | | | | SM00006 | 8 | | | ALL |
| 205R | 18 | HM | E | 0-0 | 78-36-21 | D04254P | 24 | | | | D04164J | 7 | | | ALL |
| 206B | 18 | HM | F | 14-7 | 78-36-21 | D04254P | 25 | | | | SM00004 | 8 | | | ALL |
| 206R | 18 | HM | F | 0-0 | 78-36-21 | D04254P | 26 | | | | D04166J | 12 | | | ALL |
| 207B | 18 | HM | G | 14-7 | 78-36-21 | D04254P | 27 | | | | SM00005 | 8 | | | ALL |
| 207R | 18 | HM | G | 0-0 | 78-36-21 | D04254P | 28 | | | | D04166J | 14 | | | ALL |
| 215B | 20 | HQ | IO | 6-5 | 78-36-21 | D04166J | 16 | | | | SP09599 | 8 | | | ALL |
| 215R | 20 | HQ | IO | 0-0 | 78-36-21 | D04166J | 15 | | | | SP09601 | 8 | | | ALL |
| 215Z | | | IO | 0-0 | 78-36-21 | D04166J | = CC | M | | | SP09599 | REF | V | | ALL |
| 216B | 20 | HQ | IP | 4-11 | 78-36-21 | D04164J | 2 | | | | SP09599 | 8 | | | ALL |
| 216R | 20 | HQ | IP | 0-0 | 78-36-21 | D04164J | 3 | | | | SP09601 | 8 | | | ALL |
| 216Z | | | IP | 0-0 | 78-36-21 | D04164J | = CC | M | | | SP09599 | REF | V | | 050-099, 150-199 |
| 216Z | | | IP | 0-0 | 78-36-21 | D04164J | = CC | L | | | SP09599 | REF | V | | 275-299 |
| 301B | 20 | HR | J | 7-5 | 36-23-21 | D04248P | 13 | | | | D00068 | 5 | | | ALL |
| 301R | 20 | HR | J | 0-0 | 36-23-21 | D04248P | 14 | | | | D00068 | 6 | | | ALL |
| 301Y | 20 | HR | J | 0-0 | 36-23-21 | D04248P | 15 | | | | D00068 | 7 | | | ALL |
| 301Z | | | J | 0-0 | 36-23-21 | D04248P | 16 | | | | D00068 | DED | | | ALL |
| 302B | 18 | HR | MB | 10-0 | 73-31-11 | D04252P | 18 | | | | D04258J | 18 | | | ALL |
| 302R | 18 | HR | MB | 0-0 | 73-31-11 | D04252P | 17 | | | | D04258J | 17 | | | ALL |
| 302Y | 18 | HR | MB | 0-0 | 73-31-11 | D04252P | 19 | | | | D04258J | 19 | | | ALL |
| 302Z | | | MB | 0-0 | 73-31-11 | D04252P | = CC | M | | | D04258J | = CC | M | | ALL |
| 304B | 18 | HR | MD | 10-0 | 73-33-11 | D04258J | 25 | | | | D04252P | 29 | | | 050-099, 155-199, 275-299 |
| 304B | 18 | HR | MD | 10-0 | MULTI | D04258J | 25 | | | | D04252P | 29 | | | 150-154 |
| 304R | 18 | HR | MD | 0-0 | 73-33-11 | D04258J | 23 | | | | D04252P | 27 | | | 050-099, 155-199, 275-299 |
| 304R | 18 | HR | MD | 0-0 | MULTI | D04258J | 23 | | | | D04252P | 27 | | | 150-154 |
| 304Y | 18 | HR | MD | 0-0 | 73-33-11 | D04258J | 24 | | | | D04252P | 28 | | | 050-099, 155-199, 275-299 |
| 304Y | 18 | HR | MD | 0-0 | MULTI | D04258J | 24 | | | | D04252P | 28 | | | 150-154 |
| 304Z | | | MD | 0-0 | 73-33-11 | D04258J | = CC | M | | | D04252P | = CC | M | | 050-099, 155-199, 275-299 |
| 304Z | | | MD | 0-0 | MULTI | D04258J | = CC | M | | | D04252P | = CC | M | | 150-154 |
| 306B | 18 | HR | MF | 10-0 | 79-31-11 | D04252P | 12 | | | | D04258J | 12 | | | ALL |
| 306R | 18 | HR | MF | 0-0 | 79-31-11 | D04252P | 14 | | | | D04258J | 14 | | | ALL |
| 306Y | 18 | HR | MF | 0-0 | 79-31-11 | D04252P | 13 | | | | D04258J | 13 | | | ALL |
| 306Z | | | MF | 0-0 | 79-31-11 | D04252P | = CC | M | | | D04258J | = CC | M | | ALL |
| 400R | 18 | 9P | | 7-2 | 26-18-22 | D04254P | 14 | | | | TS0238 | = 1 | D1 | * | ALL |

WIRE LIST
D280T132

91-21-11
Section W0370
Page 10
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|----------|---------|------|--------|-------|------|---------|--------|-------------|---|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0376 | 286T0376 | | | R. STRUT-R2B-ENG INSTR (continued) | | | | | | | | | | | | | |
| 451R | 18 | | 9P | 7-5 | 26-18-22 | D04254P | | 21 | | | | | TS0239 | =1 | D1 | * | ALL |
| 453R | 18 | | 9P | 3-6 | 26-18-22 | TS0238 | | =1 | D1 | * | | | TS0239 | =1 | D1 | * | ALL |
| 454R | 18 | | 9P | 3-10 | 26-18-22 | TS0238 | | =2 | D1 | | | | GD05250 | D.. | E1 | | ALL |
| 455R | 18 | | 9P | 1-3 | 26-18-22 | TS0239 | | =2 | D1 | | | | GD05250 | D.. | E1 | | ALL |
| 459R | 18 | | 9P | 6-11 | 26-18-21 | D10590 | | =1 | | | | | D04248P | | 24 | | ALL |
| W0377 | 286T0377 | | | HF-L COAX,COUPLER,ANT. | | | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-11-11 | D00001 | | =C1 | | | | D04839P | =C1 | | | ALL |
| 01CX | | | | BS | A | 1-5 | 23-11-11 | D00001 | =A1 | | | | D04839P | =A1 | | | 050-099, 150-154, 162-164, 275-276 |
| 01CX | | | | 65 | A | 1-5 | 23-11-11 | D00001 | =A1 | | | | D04839P | =A1 | | | 155-157, 165-199, 277-299 |
| W0378 | 286T0378 | | | R STRUT-S2B-FIRE DETECTION | | | | | | | | | | | | | |
| 451R | 16 | | 9P | 9-6 | 26-11-22 | D04264P | | 1 | | | | | D04256J | 1 | | | ALL |
| 452R | 16 | | 9P | 9-6 | 26-11-21 | D04264P | | 2 | | | | | D04256J | 2 | | | ALL |
| 453R | 16 | | 9P | 9-6 | SPARE | D04264P | | 3 | | | | | D04256J | 3 | | | ALL |
| 454R | 16 | | 9P | 9-7 | 26-11-22 | D04264P | | 4 | | | | | D04148J | 1 | | | ALL |
| 455R | 16 | | 9P | 9-7 | 26-11-21 | D04264P | | 5 | | | | | D04148J | 2 | | | ALL |
| 456R | 16 | | 9P | 9-7 | 26-11-21 | D04264P | | 6 | | | | | D04148J | 3 | | | ALL |
| 457R | 16 | | 9P | 9-7 | 26-11-22 | D04264P | | 7 | | | | | D04148J | 4 | | | ALL |
| W0379 | 286T0379 | | | HF-R COAX,COUPLER,ANT. | | | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-11-21 | D04841P | | =C1 | | | | D00003 | =C1 | | | ALL |
| 01CX | | | | BS | A | 3-0 | 23-11-21 | D04841P | =A1 | | | | D00003 | =A1 | | | 050-099, 150-154, 162-164, 275 |
| 01CX | | | | 65 | A | 3-0 | 23-11-21 | D04841P | =A1 | | | | D00003 | =A1 | | | 155-157, 165-199, 276-299 |

WIRE LIST

D280T132

91-21-11

Section W0370

Page 11 End

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0380 | 286T0380 | | | L. STRUT-ENGINE AIDS/AUTOSTART | | | | | | | | | | | |
| 01TI | | | | S | 0-0 | 77-31-11 | D06292P | | 3 | | D06420J | | 3 | | 050-099, 155-199, 277-299 |
| 01TO | | | | S | 0-0 | 77-31-11 | D06292P | =CC | M | | D06420J | =CC | M | | 050-099, 155-199, 277-299 |
| 01TR | 20 | | RQ | S | 14-0 | 77-31-11 | D06292P | | 2 | | D06420J | | 2 | | 050-099, 155-199, 277-299 |
| 01TW | 20 | | RQ | S | 0-0 | 77-31-11 | D06292P | | 1 | | D06420J | | 1 | | 050-099, 155-199, 277-299 |
| 027 | 16 | | HL | | 3-1 | 73-21-13 | GD05192 | S.. | N | | D06420J | | 4 | | ALL |
| 028 | 16 | | HL | | 2-9 | 73-21-13 | GD05194 | S.. | N | | D06420J | | 5 | | ALL |
| 201R | 20 | | RJ | S | 14-0 | 77-31-11 | D06292P | | 2 | | D06420J | | 2 | | 150-154, 275-276 |
| 201W | 20 | | RJ | S | 0-0 | 77-31-11 | D06292P | | 1 | | D06420J | | 1 | | 150-154, 275-276 |
| 201Z | | | | S | 0-0 | 77-31-11 | D06292P | | 3 | | D06420J | | 3 | | 150-154, 275-276 |
| 301B | 20 | | HR | MA | 14-0 | SPARE | D06420J | | 6 | | D06292P | | 7 | | 050-099, 155-157, 164-199, 277-299 |
| 301R | 20 | | HR | MA | 0-0 | SPARE | D06420J | | 8 | | D06292P | | 6 | | 050-099, 155-157, 164-199, 277-299 |
| 301Y | 20 | | HR | MA | 0-0 | SPARE | D06420J | | 7 | | D06292P | | 8 | | 050-099, 155-157, 164-199, 277-299 |
| 301Z | | | | MA | 0-0 | SPARE | D06420J | =CC | M | | D06292P | =CC | M | | 050-099, 155-157, 164-199, 277-299 |
| W0382 | 286T0382 | | | R. STRUT-R2-EEC | | | | | | | | | | | |
| 002 | 16 | | HP | B | 16-10 | 73-21-20 | D04244P | | 13 | | D04246J | | 13 | | ALL |
| 002Z | | | | B | 0-0 | 73-21-20 | D04244P | =CC | M | | D04246J | =CC | M | | ALL |
| 003 | 16 | | HP | AC | 13-6 | 73-21-11 | D04244P | | 4 | | SP03120 | | 8 | | ALL |
| 003Z | | | | AC | 0-0 | 73-21-11 | D04244P | =CC | M | | SP03120 | REF | V | | ALL |
| 006 | 20 | | HP | AF | 6-5 | 73-21-11 | SP03104 | | 8 | | D04246J | | 8 | | ALL |
| 006Z | | | | AF | 0-0 | 73-21-11 | SP03104 | REF | V | | D04246J | =CC | M | | ALL |
| 010 | 16 | | HP | AJ | 6-5 | 73-21-11 | SP03120 | | 8 | | D04246J | | 4 | | ALL |
| 010Z | | | | AJ | 0-0 | 73-21-11 | SP03120 | REF | V | | D04246J | =CC | M | | ALL |
| 014 | 20 | | HP | AN | 13-6 | 73-21-11 | D04244P | | 8 | | SP03104 | | 8 | | ALL |
| 014Z | | | | AN | 0-0 | 73-21-11 | D04244P | =CC | M | | SP03104 | REF | V | | ALL |
| 025 | 16 | | HP | CA | 16-10 | SPARE | D04244P | | 37 | | D04246J | | 37 | | ALL |
| 025Z | | | | CA | 0-0 | SPARE | D04244P | =CC | M | | D04246J | =CC | M | | ALL |
| 040 | 20 | | HP | BO | 4-10 | 73-21-11 | SP03100 | | 8 | | D04246J | | 7 | | ALL |
| 040Z | | | | BO | 0-0 | 73-21-11 | SP03100 | REF | V | | D04246J | =CC | M | | ALL |
| 041 | 20 | | HP | BP | 14-6 | 73-21-11 | D04244P | | 7 | | SP03100 | | 8 | | ALL |
| 041Z | | | | BP | 0-0 | 73-21-11 | D04244P | =CC | M | | SP03100 | REF | V | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0380
Page 1
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0382 | 286T0382 | | | R. STRUT-R2-EEC (continued) | | | | | | | | | | | |
| 101 | 20 | HP | EA | 4-10 | 78-36-21 | D04246J | 34 | | | SP09587 | 8 | | | ALL | |
| 101Z | | | EA | 0-0 | 78-36-21 | D04246J | = CC | M | | SP09587 | REF | V | | ALL | |
| 102 | 20 | HP | EB | 4-10 | 78-36-21 | D04246J | 31 | | | SP09589 | 8 | | | ALL | |
| 102Z | | | EB | 0-0 | 78-36-21 | D04246J | = CC | M | | SP09589 | REF | V | | ALL | |
| 107 | 20 | HP | EG | 5-4 | 73-21-14 | D04246J | 11 | | | SP03258 | 8 | | | ALL | |
| 107Z | | | EG | 0-0 | 73-21-14 | D04246J | = CC | M | | SP03258 | REF | V | | ALL | |
| 108 | 20 | HP | P | 14-0 | 73-21-19 | D04244P | 40 | | | SP03116 | 8 | | | ALL | |
| 108Z | | | P | 0-0 | 73-21-19 | D04244P | = CC | M | | SP03116 | REF | V | | ALL | |
| 109 | 20 | HP | H | 5-4 | 73-21-19 | SP03116 | 8 | | | D04246J | 18 | | | ALL | |
| 109Z | | | H | 0-0 | 73-21-19 | SP03116 | REF | V | | D04246J | = CC | M | | ALL | |
| 110 | 20 | HP | R | 14-0 | SPARE | D04244P | 11 | | | SP03258 | 8 | | | ALL | |
| 110Z | | | R | 0-0 | SPARE | D04244P | = CC | M | | SP03258 | REF | V | | ALL | |
| 123 | 20 | HP | EW | 4-10 | 78-36-21 | SP03342 | 8 | | | D04246J | 19 | | | ALL | |
| 123Z | | | EW | 0-0 | 78-36-21 | SP03342 | REF | V | | D04246J | = CC | M | | ALL | |
| 130 | 20 | HP | AY | 14-6 | 73-21-17 | D04244P | 1 | | | SP03476 | 8 | | | ALL | |
| 130Z | | | AY | 0-0 | 73-21-17 | D04244P | = CC | M | | SP03476 | REF | V | | ALL | |
| 131 | 20 | HP | AZ | 4-10 | 73-21-17 | D04246J | 42 | | | SP03476 | 8 | | | ALL | |
| 131Z | | | AZ | 0-0 | 73-21-17 | D04246J | = CC | M | | SP03476 | REF | V | | ALL | |
| 201B | 20 | HQ | T | 16-10 | 77-12-12 | D04244P | 2 | | | D04246J | 3 | | | ALL | |
| 201R | 20 | HQ | T | 0-0 | 77-12-12 | D04244P | 3 | | | D04246J | 2 | | | ALL | |
| 201Z | | | T | 0-0 | 77-12-12 | D04244P | = CC | M | | D04246J | = CC | M | | ALL | |
| 202B | 20 | HQ | AA | 16-10 | 73-21-13 | D04244P | 15 | | | D04246J | 15 | | | ALL | |
| 202R | 20 | HQ | AA | 0-0 | 73-21-13 | D04244P | 16 | | | D04246J | 16 | | | ALL | |
| 202Z | | | AA | 0-0 | 73-21-13 | D04244P | = CC | M | | D04246J | = CC | M | | ALL | |
| 203B | 20 | HQ | CB | 6-5 | 73-21-14 | SP03114 | 8 | | | D04246J | 6 | | | ALL | |
| 203R | 20 | HQ | CB | 0-0 | 73-21-14 | SP03110 | 8 | | | D04246J | 5 | | | ALL | |
| 203Z | | | CB | 0-0 | 73-21-14 | SP03110 | REF | V | | D04246J | = CC | M | | ALL | |
| 204B | 20 | HQ | AD | 16-10 | 73-21-14 | D04244P | 23 | | | D04246J | 24 | | | ALL | |
| 204R | 20 | HQ | AD | 0-0 | 73-21-14 | D04244P | 24 | | | D04246J | 23 | | | ALL | |
| 204Z | | | AD | 0-0 | 73-21-14 | D04244P | = CC | M | | D04246J | = CC | M | | ALL | |
| 207B | 20 | HQ | V | 16-10 | SPARE | D04244P | 36 | | | D04246J | 36 | | | 050-099, 150-199, 275-276, 278-299 | |
| 207B | 20 | HQ | V | 17-0 | 31-35-15 | D04244P | 36 | | | D08334J | 11 | | | 277 | |
| 207R | 20 | HQ | V | 0-0 | SPARE | D04244P | 35 | | | D04246J | 35 | | | 050-099, 150-199, 275-276, 278-299 | |
| 207R | 20 | HQ | V | 0-0 | 31-35-15 | D04244P | 35 | | | D08334J | 10 | | | 277 | |
| 207Z | | | V | 0-0 | SPARE | D04244P | = CC | M | | D04246J | = CC | M | | 050-099, 150-199, 275-276, 278-299 | |
| 207Z | | | V | 0-0 | 31-35-15 | D04244P | = CC | M | | D08334J | = CC | M | | 277 | |

WIRE LIST

D280T132

91-21-11

Section W0380

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0382 | 286T0382 | | | R. STRUT-R2-EEC (continued) | | | | | | | | | | | |
| 208B | 20 | HQ | IH | 2-0 | 73-21-14 | D04246J | | 12 | | | SM00001 | | VH | | 050-099 |
| 208B | 20 | HQ | IH | 2-0 | 73-21-14 | D04246J | | 12 | | | SM00001 | | 8 | | 150-199, 275-299 |
| 208R | 20 | HQ | IH | 0-0 | 73-21-14 | D04246J | | 21 | | | SM00001 | | VH | | 050-099 |
| 208R | 20 | HQ | IH | 0-0 | 73-21-14 | D04246J | | 21 | | | SM00001 | | 8 | | 150-199, 275-299 |
| 208Z | | | IH | 0-0 | 73-21-14 | D04246J | | = CC | M | | SM00001 | REF | VH | | 050-099 |
| 208Z | | | IH | 0-0 | 73-21-14 | D04246J | | = CC | M | | SM00001 | REF | V | | 150-199, 275-299 |
| 209B | 20 | HQ | II | 2-0 | 73-21-14 | D04246J | | 20 | | | SM00001 | | 8 | | 150-152, 154-199, 275-299 |
| 209R | 20 | HQ | II | 0-0 | 73-21-14 | D04246J | | 1 | | | SM00001 | | 8 | | 150-152, 154-199, 275-299 |
| 209Z | | | II | 0-0 | 73-21-14 | D04246J | | = CC | M | | SM00001 | REF | V | | 150-152, 154-199, 275-299 |
| 210B | 20 | HQ | K | 5-4 | 73-21-14 | SP03106 | | | 8 | | D04246J | | 33 | | ALL |
| 210R | 20 | HQ | K | 0-0 | 73-21-14 | SP03102 | | | 8 | | D04246J | | 32 | | ALL |
| 210Z | | | K | 0-0 | 73-21-14 | SP03102 | | REF | V | | D04246J | = CC | M | | ALL |
| 218B | 20 | HQ | IR | 6-5 | 78-36-21 | D04246J | | 30 | | | SP09591 | | 8 | | ALL |
| 218R | 20 | HQ | IR | 0-0 | 78-36-21 | D04246J | | 29 | | | SP09593 | | 8 | | ALL |
| 218Z | | | IR | 0-0 | 78-36-21 | D04246J | | = CC | M | | SP09591 | REF | V | | ALL |
| 220B | 20 | HQ | IT | 14-0 | 73-21-14 | D04244P | | 6 | | | SP03106 | | 8 | | ALL |
| 220R | 20 | HQ | IT | 0-0 | 73-21-14 | D04244P | | 5 | | | SP03102 | | 8 | | ALL |
| 220Z | | | IT | 0-0 | 73-21-14 | D04244P | | = CC | M | | SP03106 | REF | V | | ALL |
| 226B | 20 | HQ | JA | 5-4 | 73-21-14 | D04246J | | 10 | | | SP03208 | | 8 | | ALL |
| 226R | 20 | HQ | JA | 0-0 | 73-21-14 | D04246J | | 9 | | | SP03204 | | 8 | | ALL |
| 226Z | | | JA | 0-0 | 73-21-14 | D04246J | | = CC | M | | SP03204 | REF | V | | ALL |
| 227B | 20 | HQ | JB | 16-10 | 73-21-17 | D04244P | | 28 | | | D04246J | | 28 | | ALL |
| 227R | 20 | HQ | JB | 0-0 | 73-21-12 | D04244P | | 17 | | | D04246J | | 17 | | ALL |
| 227Z | | | JB | 0-0 | 73-21-12 | D04244P | | = CC | M | | D04246J | = CC | M | | ALL |
| 301B | 20 | HR | AB | 16-10 | 73-21-13 | D04244P | | 27 | | | D04246J | | 27 | | ALL |
| 301R | 20 | HR | AB | 0-0 | 73-21-13 | D04244P | | 26 | | | D04246J | | 26 | | ALL |
| 301Y | 20 | HR | AB | 0-0 | 73-21-13 | D04244P | | 25 | | | D04246J | | 25 | | ALL |
| 301Z | | | AB | 0-0 | 73-21-13 | D04244P | | = CC | M | | D04246J | = CC | M | | ALL |
| 304B | 20 | HR | II | 4-0 | 73-21-14 | D04246J | | 20 | | | SM00001 | | VH | | 050-099 |
| 304B | 20 | HR | A0 | 4-0 | 73-21-14 | D04246J | | 20 | | | SM00001 | | 8 | | 153 |
| 304R | 20 | HR | II | 0-0 | 73-21-14 | D04246J | | 1 | | | SM00001 | | VH | | 050-099 |
| 304R | 20 | HR | A0 | 0-0 | 73-21-14 | D04246J | | 1 | | | SM00001 | | 8 | | 153 |
| 304Y | 20 | HR | II | 0-0 | 73-21-14 | D04246J | | 41 | | | SM00001 | | VH | | 050-099 |
| 304Y | 20 | HR | A0 | 0-0 | 73-21-14 | D04246J | | 41 | | | SM00001 | | 8 | | 153 |
| 304Z | | | II | 0-0 | 73-21-14 | D04246J | | = CC | M | | SM00001 | REF | VH | | 050-099 |
| 304Z | | | A0 | 0-0 | 73-21-14 | D04246J | | = CC | M | | SM00001 | | 8 | | 153 |

WIRE LIST
D280T132

91-21-11
Section W0380
Page 3
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0382 | 286T0382 | | | R. STRUT-R2-EEC (continued) | | | | | | | | | | | | |
| 305B | 20 | HR | W | 16-10 | 73-21-11 | D04244P | 10 | | | | D04246J | 40 | | | ALL | |
| 305R | 20 | HR | W | 0-0 | 73-21-11 | D04244P | 19 | | | | D04246J | 39 | | | ALL | |
| 305Y | 20 | HR | W | 0-0 | 73-21-11 | D04244P | 9 | | | | D04246J | 38 | | | ALL | |
| 305Z | | | W | 0-0 | 73-21-11 | D04244P | = CC | M | | | D04246J | = CC | M | | ALL | |
| W0384 | 286T0384 | | | R. STRUT-ENGINE AIDS/AUTOSTART | | | | | | | | | | | | |
| 01TI | | | S | 0-0 | 77-31-11 | D06296P | 3 | | | | D06422J | 3 | | | 050-099, 155-199, 277-299 | |
| 01TO | | | S | 0-0 | 77-31-11 | D06296P | = CC | M | | | D06422J | = CC | M | | 050-099, 155-199, 277-299 | |
| 01TR | 20 | RQ | S | 14-3 | 77-31-11 | D06296P | 2 | | | | D06422J | 2 | | | 050-099, 155-199, 277-299 | |
| 01TW | 20 | RQ | S | 0-0 | 77-31-11 | D06296P | 1 | | | | D06422J | 1 | | | 050-099, 155-199, 277-299 | |
| 027 | 16 | HL | | 3-1 | 73-21-13 | GD05258 | S.. | N | | | D06422J | 4 | | | ALL | |
| 028 | 16 | HL | | 2-9 | 73-21-13 | GD05260 | S.. | N | | | D06422J | 5 | | | ALL | |
| 201R | 20 | RJ | S | 14-3 | 77-31-11 | D06296P | 2 | | | | D06422J | 2 | | | 150-154, 275-276 | |
| 201W | 20 | RJ | S | 0-0 | 77-31-11 | D06296P | 1 | | | | D06422J | 1 | | | 150-154, 275-276 | |
| 201Z | | | S | 0-0 | 77-31-11 | D06296P | 3 | | | | D06422J | 3 | | | 150-154, 275-276 | |
| 301B | 20 | HR | MA | 14-3 | SPARE | D06422J | 6 | | | | D06296P | 7 | | | 050-099, 155-157, 164-199, 277-299 | |
| 301R | 20 | HR | MA | 0-0 | SPARE | D06422J | 8 | | | | D06296P | 6 | | | 050-099, 155-157, 164-199, 277-299 | |
| 301Y | 20 | HR | MA | 0-0 | SPARE | D06422J | 7 | | | | D06296P | 8 | | | 050-099, 155-157, 164-199, 277-299 | |
| 301Z | | | MA | 0-0 | SPARE | D06422J | = CC | M | | | D06296P | = CC | M | | 050-099, 155-157, 164-199, 277-299 | |
| W0386 | 286T0386 | | | L STRUT-S2A-FIRE DETECTION/ENG INSTR | | | | | | | | | | | | |
| 001 | 18 | HL | | 10-5 | 80-11-11 | D04204P | 4 | | | | D04230J | 4 | | | ALL | |
| 002 | 18 | HP | AB | 10-5 | 80-11-11 | D04204P | 5 | | | | D04230J | 5 | | | ALL | |
| 002Z | | | AB | 0-0 | 80-11-11 | D04204P | = CC | M | | | D04230J | = CC | M | | ALL | |
| 003 | 18 | HP | AC | 10-5 | 80-11-11 | D04204P | 6 | | | | D04230J | 6 | | | ALL | |
| 003Z | | | AC | 0-0 | 80-11-11 | D04204P | = CC | M | | | D04230J | = CC | M | | ALL | |
| 005 | 18 | HL | | 10-5 | 76-11-11 | D04204P | 8 | | | | D04230J | 8 | | | ALL | |
| 006 | 18 | HP | AF | 10-5 | 76-11-11 | D04204P | 9 | | | | D04230J | 9 | | | ALL | |
| 006Z | | | AF | 0-0 | 76-11-11 | D04204P | = CC | M | | | D04230J | = CC | M | | ALL | |
| 007 | 18 | HL | | 10-5 | 76-11-11 | D04204P | 10 | | | | D04230J | 10 | | | ALL | |
| 009 | 18 | HP | AI | 10-5 | 76-11-11 | D04204P | 12 | | | | D04230J | 12 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0380

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0386 | 286T0386 | | | | L STRUT-S2A-FIRE DETECTION/ENG INSTR (continued) | | | | | | | | | | |
| 009Z | | | | AI | 0-0 | 76-11-11 | D04204P | =CC | M | | D04230J | =CC | M | | ALL |
| 451R | 16 | | 9P | | 10-2 | 26-11-12 | D04204P | | 1 | | D04200J | | 1 | | ALL |
| 452R | 16 | | 9P | | 10-2 | 26-11-11 | D04204P | | 2 | | D04200J | | 2 | | ALL |
| 453R | 16 | | 9P | | 10-2 | SPARE | D04204P | | 3 | | D04200J | | 3 | | ALL |
| 454R | 16 | | 9P | | 10-5 | 26-11-12 | D04204P | | 14 | | D04230J | | 14 | | ALL |
| 455R | 16 | | 9P | | 10-5 | 26-11-11 | D04204P | | 15 | | D04230J | | 15 | | ALL |
| 456R | 16 | | 9P | | 10-5 | 26-11-11 | D04204P | | 16 | | D04230J | | 16 | | ALL |
| 457R | 16 | | 9P | | 10-5 | 26-11-12 | D04204P | | 18 | | D04230J | | 18 | | ALL |
| 458R | 16 | | 9P | | 10-5 | SPARE | D04204P | | 13 | | D04230J | | 13 | | ALL |
| W0388 | 286T0388 | | | | R STRUT-S2A-FIRE DETECTION/ENG INSTR | | | | | | | | | | |
| 001 | 18 | | HL | | 13-0 | 80-11-21 | D04238P | | 4 | | D04220J | | 4 | | ALL |
| 002 | 18 | | HP | AB | 13-0 | 80-11-21 | D04238P | | 5 | | D04220J | | 5 | | ALL |
| 002Z | | | | AB | 0-0 | 80-11-21 | D04238P | =CC | M | | D04220J | =CC | M | | ALL |
| 003 | 18 | | HP | AC | 13-0 | 80-11-21 | D04238P | | 6 | | D04220J | | 6 | | ALL |
| 003Z | | | | AC | 0-0 | 80-11-21 | D04238P | =CC | M | | D04220J | =CC | M | | ALL |
| 005 | 18 | | HL | | 13-0 | 76-11-11 | D04238P | | 8 | | D04220J | | 8 | | ALL |
| 006 | 18 | | HP | AF | 13-0 | 76-11-11 | D04238P | | 9 | | D04220J | | 9 | | ALL |
| 006Z | | | | AF | 0-0 | 76-11-11 | D04238P | =CC | M | | D04220J | =CC | M | | ALL |
| 007 | 18 | | HL | | 13-0 | 76-11-11 | D04238P | | 10 | | D04220J | | 10 | | ALL |
| 009 | 18 | | HP | AI | 13-0 | 76-11-11 | D04238P | | 12 | | D04220J | | 12 | | ALL |
| 009Z | | | | AI | 0-0 | 76-11-11 | D04238P | =CC | M | | D04220J | =CC | M | | ALL |
| 451R | 16 | | 9P | | 12-10 | 26-11-22 | D04238P | | 1 | | D04236J | | 1 | | ALL |
| 452R | 16 | | 9P | | 12-10 | 26-11-21 | D04238P | | 2 | | D04236J | | 2 | | ALL |
| 453R | 16 | | 9P | | 12-10 | SPARE | D04238P | | 3 | | D04236J | | 3 | | ALL |
| 454R | 16 | | 9P | | 13-0 | 26-11-22 | D04238P | | 14 | | D04220J | | 14 | | ALL |
| 455R | 16 | | 9P | | 13-0 | 26-11-21 | D04238P | | 15 | | D04220J | | 15 | | ALL |
| 456R | 16 | | 9P | | 13-0 | 26-11-21 | D04238P | | 16 | | D04220J | | 16 | | ALL |
| 457R | 16 | | 9P | | 13-0 | 26-11-22 | D04238P | | 18 | | D04220J | | 18 | | ALL |
| 458R | 16 | | 9P | | 13-0 | SPARE | D04238P | | 13 | | D04220J | | 13 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0380
Page 5 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|----------|---------|------|------|---------|---------|------|------|------------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0390 | 286T0390 | | | L SAILBOAT-L2-HYDRAULICS | | | | | | | | | | | | |
| 001 | 18 | | HL | 6-0 | 78-34-11 | GD02398 | D.. | N | | D02118 | | 1 | | ALL | | |
| 002 | 18 | | HL | 8-0 | 78-34-11 | D04474J | | 2 | | D02118 | CAP | Y | | ALL | | |
| 003 | 18 | | HL | 8-0 | 78-34-11 | D04474J | | 3 | | D02118 | | 3 | | ALL | | |
| 004 | 18 | | HL | 7-0 | 29-32-11 | D04474J | | 9 | | D00498 | | 1 | | ALL | | |
| 006 | 18 | | HL | 4-0 | 29-32-11 | GD02398 | D.. | N | | D00498 | | 2 | | ALL | | |
| 007 | 18 | | HL | 8-0 | 29-32-11 | D04474J | | 5 | | GD02398 | D.. | N | | ALL | | |
| 008 | 18 | | HL | 8-0 | 78-36-11 | D04474J | | 6 | | D02134 | | 1 | | ALL | | |
| 009 | 18 | | HL | 9-0 | SPARE | D04474J | CAP | Y | | D02134 | CAP | Y | | ALL | | |
| 010 | 18 | | HL | 8-0 | SPARE | D04474J | | 8 | | D02134 | CAP | Y | | 050-099, 150-166, 275-276 | | |
| 010 | 18 | | HL | 8-0 | 78-36-11 | D04474J | | 8 | | D02134 | CAP | Y | | 167-199, 277-299 | | |
| 011 | 20 | | HP | A | 7-0 | 29-33-11 | D04474J | | 12 | | D00038 | | 7 | ALL | | |
| 011Z | | | A | | 0-0 | 29-33-11 | D04474J | | | FB | D00038 | | | FA | ALL | |
| 012 | 18 | | HL | | 7-0 | 29-33-11 | D04474J | | 14 | | D00038 | | 5 | ALL | | |
| 013 | 18 | | HL | | 7-0 | 29-33-11 | D04474J | | 15 | | D00038 | | 3 | ALL | | |
| 014 | 18 | | HL | | 7-0 | 29-33-11 | D04474J | | 10 | | D00038 | | 4 | ALL | | |
| 015 | 18 | | HL | | 5-0 | 29-33-11 | GD02400 | S.. | N | | D00038 | | 2 | ALL | | |
| 018 | 18 | | HL | | 5-0 | 29-11-11 | GD02396 | D.. | N | | D00494 | | E | ALL | | |
| 019 | 18 | | HL | | 6-0 | 29-32-11 | D00036 | | 2 | | GD02398 | D.. | N | ALL | | |
| 020 | 18 | | HL | | 9-0 | 29-32-11 | D00036 | | 1 | | D04474J | | 16 | ALL | | |
| 021 | 18 | | HL | | 6-0 | 29-11-12 | D00054 | | 2 | | GD02396 | D.. | N | ALL | | |
| 022 | 18 | | HL | | 9-0 | 29-11-12 | D00054 | | 3 | | D04474J | | 17 | ALL | | |
| 026 | 18 | | HL | | 6-0 | 29-32-11 | D00036 | | 3 | | GD02400 | S.. | N | ALL | | |
| 027 | 18 | | HL | | 5-0 | 29-32-11 | D00498 | | 3 | | GD02400 | S.. | N | ALL | | |
| 028 | 18 | | HL | | 6-0 | 78-36-11 | GD02396 | D.. | N | | D02134 | | 2 | ALL | | |
| 081 | 18 | | HL | | 15-0 | 78-36-11 | D20122 | | 1 | | D04474J | | 19 | ALL | | |
| 082 | 18 | | HL | | 15-0 | 78-36-11 | D20122 | | 2 | | GD02396 | D.. | N | ALL | | |
| 083 | 18 | | HL | | 15-0 | 78-36-11 | D20122 | | 3 | | D04474J | | 18 | ALL | | |
| 100 | 18 | | HL | | 15-0 | 78-34-11 | GD02410 | D.. | N | | D20118 | | 1 | ALL | | |
| 101 | 18 | | HL | | 15-0 | 78-34-11 | GD02400 | S.. | N | | D04474J | | | FD | ALL | |
| 102 | 18 | | HP | C | 15-0 | 78-34-11 | D04474J | | 1 | | D20118 | | 3 | ALL | | |
| 102Z | | | C | | 0-0 | 78-34-11 | D04474J | | | FD | D20118 | DED | | ALL | | |
| 103 | 18 | | HP | D | 15-0 | 78-34-11 | D04474J | | 7 | | D20118 | | 2 | ALL | | |
| 103Z | | | D | | 0-0 | 78-34-11 | D04474J | | | FD | D20118 | DED | | ALL | | |
| 201B | 20 | | HQ | B | 8-0 | 29-11-11 | D04404J | | 1 | | D00494 | | A | ALL | | |
| 201R | 20 | | HQ | B | 0-0 | 29-11-11 | D04404J | | 2 | | D00494 | | B | ALL | | |
| 201Z | | | B | | 0-0 | 29-11-11 | D04404J | DED | | | D00494 | DED | | ALL | | |
| FRA | | | | | 0-0 | 29-33-11 | D00038 | | | FA | D00038 | | 1 | ALL | | |
| FRB | | | | | 0-0 | 29-33-11 | D00038 | | | FA | D00038 | | 6 | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0390

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0390 | 286T0390 | | | L SAILBOAT-L2-HYDRAULICS (continued) | | | | | | | | | | | |
| FRC | | | | 0-0 | 29-33-11 | D04474J | | | | FB | D04474J | 4 | | ALL | |
| FRD | | | | 0-0 | 29-33-11 | D04474J | | | | FB | D04474J | 11 | | ALL | |
| FRE | | | | 0-0 | 29-33-11 | D04474J | | | | FB | D04474J | 13 | | ALL | |
| W0391 | 286T0391 | | | RDMI-L,SHELVES TO CAPT INSTR PNL | | | | | | | | | | | |
| 002 | 24 | | PK | 31-0 | 31-31-13 | D04151J | | 2 | | | D04147J | 21 | | ALL | |
| 003 | 24 | | PK | 31-0 | 31-31-13 | D04151J | | 3 | | | D04147J | 22 | | ALL | |
| 004 | 22 | | PA | 31-0 | 34-22-17 | D04151J | | 4 | | | D04147J | 4 | | ALL | |
| 005 | 22 | | PA | 31-0 | 34-32-11 | D04151J | | 5 | | | D04147J | 5 | | ALL | |
| 006 | 22 | | PA | 31-0 | 34-32-11 | D04151J | | 6 | | | D04147J | 6 | | ALL | |
| 007 | 22 | | PA | 31-0 | 34-32-11 | D04151J | | 7 | | | D04147J | 7 | | ALL | |
| 008 | 24 | | PK | 31-0 | 34-61-11 | D04151J | | 20 | | | D04147J | 20 | | ALL | |
| 010 | 24 | | PK | 61-0 | SPARE | D04147J | | 52 | | | D04153J | 16 | | 050-099 | |
| 011 | 24 | | PK | 61-0 | SPARE | D04147J | | 53 | | | D04153J | 17 | | 050-099 | |
| 014 | 24 | | PK | 61-0 | SPARE | D04147J | | 44 | | | D04153J | 4 | | 050-099 | |
| 015 | 22 | | PA | 61-0 | SPARE | D04147J | | 45 | | | D04153J | 5 | | 050-099 | |
| 016 | 24 | | PK | 61-0 | SPARE | D04147J | | 46 | | | D04153J | 6 | | 050-099 | |
| 017 | 24 | | PK | 61-0 | SPARE | D04147J | | 47 | | | D04153J | 7 | | 050-099 | |
| 018 | 24 | | PK | 61-0 | SPARE | D04147J | | 48 | | | D04153J | 8 | | 050-099 | |
| 037 | 24 | | PK | 31-0 | 34-12-61 | D04147J | | 37 | | | D04151J | 37 | | ALL | |
| 039 | 24 | | PK | 31-0 | 34-12-61 | D04147J | | 39 | | | D04151J | 39 | | ALL | |
| 040 | 24 | | PK | 61-0 | SPARE | D04147J | | 34 | | | D04153J | 14 | | ALL | |
| 041 | 24 | | PK | 61-0 | SPARE | D04147J | | 35 | | | D04153J | 15 | | ALL | |
| 042 | 24 | | PK | 31-0 | 34-61-15 | D04147J | | 41 | | | D04151J | 1 | | ALL | |
| 045 | 22 | | PA | 31-0 | 34-22-38 | D04147J | | 36 | | | D04151J | 36 | | ALL | |
| 201 | 20 | | UA | 1-6 | 34-22-81 | GD00401 | | S.. | 2 | | D04147J | | FC | 050-099, 150-199, 275-278 | |
| 201 | 20 | | UA | 1-6 | 34-22-81 | GD00401 | | S.. | 2 | * | D04147J | | FC | 280-299 | |
| 201B | 24 | | PW | IA | 61-0 | 34-22-81 | D04153J | | 2 | | D04147J | 2 | | ALL | |
| 201R | 24 | | PW | IA | 0-0 | 34-22-81 | D04153J | | 1 | | D04147J | 1 | | ALL | |
| 201Z | | | IA | 0-0 | 34-22-81 | D04153J | | 3 | | | D04147J | | FC | ALL | |
| 202B | 24 | | PW | IB | 31-0 | SPARE | D04151J | | 9 | | D04147J | 9 | | 150-154 | |
| 202R | 24 | | PW | IB | 0-0 | SPARE | D04151J | | 8 | | D04147J | 8 | | 150-154 | |
| 202Z | | | IB | 0-0 | SPARE | D04151J | | 10 | | | D04147J | 10 | | 150-154 | |
| 203B | 24 | | PW | IC | 31-0 | SPARE | D04151J | | 12 | | D04147J | 12 | | ALL | |
| 203R | 24 | | PW | IC | 0-0 | SPARE | D04151J | | 11 | | D04147J | 11 | | ALL | |
| 203Z | | | IC | 0-0 | SPARE | D04151J | | 16 | | | D04147J | 16 | | ALL | |
| 204 | 20 | | UA | 1-6 | 31-25-11 | D04147J | | | | FA | GD00401 | S.. | 2 | 050-099, 150-199, 275-278 | |

WIRE LIST
D280T132

91-21-11
Section W0390
Page 2
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0391 | 286T0391 | | | RDMI-L,SHELVES TO CAPT INSTR PNL (continued) | | | | | | | | | | | | |
| 204 | 20 | | UA | | 1-6 | 31-25-11 | D04147J | | | | FA | GD00401 | S.. | 2 | * | 280-299 |
| 204B | 24 | | PW | ID | 31-0 | 31-25-11 | D04151J | | 14 | | | D04147J | 14 | | | ALL |
| 204R | 24 | | PW | ID | 0-0 | 31-25-11 | D04151J | | 13 | | | D04147J | 13 | | | ALL |
| 204Z | | | | ID | 0-0 | 31-25-11 | D04151J | | 15 | | | D04147J | | | FA | ALL |
| 205 | 20 | | UA | | 1-6 | SPARE | D04147J | | | | FB | GD00401 | S.. | 2 | * | 050-099 |
| 205 | 20 | | UA | | 1-6 | SPARE | D04147J | | | | FB | GD00401 | S.. | 2 | | 150-199, 275-299 |
| 205B | 24 | | PW | IE | 31-0 | SPARE | D04151J | | 18 | | | D04147J | 18 | | | ALL |
| 205R | 24 | | PW | IE | 0-0 | SPARE | D04151J | | 17 | | | D04147J | 17 | | | ALL |
| 205Z | | | | IE | 0-0 | SPARE | D04151J | | 19 | | | D04147J | | | FB | ALL |
| 206B | 24 | | PW | IF | 31-0 | SPARE | D04147J | | 26 | | | D04151J | 26 | | | ALL |
| 206R | 24 | | PW | IF | 0-0 | SPARE | D04147J | | 27 | | | D04151J | 27 | | | ALL |
| 206Z | | | | IF | 0-0 | SPARE | D04147J | | 28 | | | D04151J | 28 | | | ALL |
| 207B | 24 | | PW | IG | 31-0 | SPARE | D04151J | | 24 | | | D04147J | 24 | | | 150-154 |
| 207R | 24 | | PW | IG | 0-0 | SPARE | D04151J | | 23 | | | D04147J | 23 | | | 150-154 |
| 207Z | | | | IG | 0-0 | SPARE | D04151J | | 25 | | | D04147J | 25 | | | 150-154 |
| 208B | 22 | | PB | IH | 31-0 | 34-12-21 | D04147J | | 30 | | | D04151J | 30 | | | ALL |
| 208R | 22 | | PB | IH | 0-0 | 34-12-21 | D04147J | | 29 | | | D04151J | 29 | | | ALL |
| 209 | 20 | | UA | | 1-6 | SPARE | D04147J | | | | FI | GD00401 | S.. | 2 | * | 050-099 |
| 209B | 24 | | PW | II | 61-0 | SPARE | D04147J | | 50 | | | D04153J | 10 | | | 050-099 |
| 209R | 24 | | PW | II | 0-0 | SPARE | D04147J | | 49 | | | D04153J | 9 | | | 050-099 |
| 209Z | | | | II | 0-0 | SPARE | D04147J | | | | FI | D04153J | 11 | | | 050-099 |
| 301B | 24 | | PM | MA | 31-0 | 34-12-21 | D04147J | | 32 | | | D04151J | 32 | | | ALL |
| 301R | 24 | | PM | MA | 0-0 | 34-12-21 | D04147J | | 31 | | | D04151J | 31 | | | ALL |
| 301Y | 24 | | PM | MA | 0-0 | 34-12-21 | D04147J | | 33 | | | D04151J | 33 | | | ALL |
| FRA | | | | | 0-0 | 31-25-11 | D04147J | | | | FA | D04147J | 15 | | | ALL |
| FRB | | | | | 0-0 | SPARE | D04147J | | | | FB | D04147J | 19 | | | ALL |
| FRC | | | | | 0-0 | 34-22-81 | D04147J | | | | FC | D04147J | 3 | | | ALL |
| FRD | | | | | 0-0 | SPARE | D04147J | | | | FI | D04147J | 51 | | | 050-099 |
| W0392 | 286T0392 | | | R. STRUT-R2-EEC-N1 ANALOG | | | | | | | | | | | | |
| 001 | 18 | | HL | | 16-9 | 30-34-21 | D06382P | | 1 | | | D08334J | 1 | | | ALL |
| 002 | 16 | | HP | A | 16-9 | 73-21-20 | D06382P | | 13 | | | D08334J | 13 | | | ALL |
| 002Z | | | | A | 0-0 | 73-21-20 | D06382P | | =CC | M | | D08334J | =CC | M | | ALL |
| 003 | 16 | | HP | AC | 5-1 | 73-21-11 | D08334J | | 4 | | | SP03120 | 8 | | | ALL |
| 003Z | | | | AC | 0-0 | 73-21-11 | D08334J | | =CC | M | | SP03120 | REF | V | | ALL |
| 014 | 20 | | HP | AN | 5-1 | 73-21-11 | D08334J | | 8 | | | SP03104 | 8 | | | ALL |
| 014Z | | | | AN | 0-0 | 73-21-11 | D08334J | | =CC | M | | SP03104 | REF | V | | ALL |
| 025 | 20 | | HP | N | 16-9 | SPARE | D06382P | | 22 | | | D08334J | 35 | | | ALL |
| 025Z | | | | N | 0-0 | SPARE | D06382P | | =CC | M | | D08334J | =CC | M | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0390

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0392 | 286T0392 | | | R. STRUT-R2-EEC-N1 ANALOG (continued) | | | | | | | | | | | |
| 100 | 20 | HP | AD | | 4-0 | 73-21-17 | D08334J | 42 | | | SP03476 | | 8 | | ALL |
| 100Z | | | AD | | 0-0 | 73-21-17 | D08334J | = CC | M | | SP03476 | REF | V | | ALL |
| 101 | 20 | HP | EA | | 4-0 | 78-36-21 | D08334J | 34 | | | SP09595 | | 8 | | ALL |
| 101Z | | | EA | | 0-0 | 78-36-21 | D08334J | = CC | M | | SP09595 | REF | V | | ALL |
| 102 | 20 | HP | EB | | 4-0 | 78-36-21 | D08334J | 31 | | | SP09597 | | 8 | | ALL |
| 102Z | | | EB | | 0-0 | 78-36-21 | D08334J | = CC | M | | SP09597 | REF | V | | ALL |
| 103 | 20 | HP | EC | | 4-7 | 73-21-14 | D08334J | 9 | | | SP03258 | | 8 | | ALL |
| 103Z | | | EC | | 0-0 | 73-21-14 | D08334J | = CC | M | | SP03258 | REF | V | | ALL |
| 107 | 20 | HP | EG | | 4-7 | 73-21-19 | SP03116 | 8 | | | D08334J | 18 | | | ALL |
| 107Z | | | EG | | 0-0 | 73-21-19 | SP03116 | REF | V | | D08334J | = CC | M | | ALL |
| 109 | 20 | HP | EF | | 13-11 | 73-21-14 | D06382P | 11 | | | SP03258 | | 8 | | ALL |
| 109Z | | | EF | | 0-0 | 73-21-14 | D06382P | = CC | M | | SP03258 | REF | V | | ALL |
| 111 | 20 | HP | IF | | 4-0 | 73-21-11 | SP03100 | 8 | | | D08334J | 7 | | | ALL |
| 111Z | | | IF | | 0-0 | 73-21-11 | SP03100 | REF | V | | D08334J | = CC | M | | ALL |
| 132 | 20 | HP | FG | | 4-0 | 78-36-21 | SP03342 | 8 | | | D08334J | 19 | | | ALL |
| 132Z | | | FG | | 0-0 | 78-36-21 | SP03342 | REF | V | | D08334J | = CC | M | | ALL |
| 201B | 20 | HQ | IA | | 16-9 | 31-35-15 | D06382P | 21 | | | D08334J | 11 | | | 050-099, 155-199, 278-299 |
| 201B | 20 | HQ | IA | | 16-9 | 31-35-15 | D08334J | 11 | | | D06382P | 21 | | | 150-154, 275-276 |
| 201R | 20 | HQ | IA | | 0-0 | 31-35-15 | D06382P | 20 | | | D08334J | 10 | | | 050-099, 155-199, 278-299 |
| 201R | 20 | HQ | IA | | 0-0 | 31-35-15 | D08334J | 10 | | | D06382P | 20 | | | 150-154, 275-276 |
| 201Z | | | IA | | 0-0 | 31-35-15 | D06382P | = CC | M | | D08334J | = CC | M | | 050-099, 155-199, 278-299 |
| 201Z | | | IA | | 0-0 | 31-35-15 | D08334J | = CC | M | | D06382P | = CC | M | | 150-154, 275-276 |
| 202B | 20 | HQ | P | | 16-9 | 73-21-13 | D06382P | 15 | | | D08334J | 15 | | | ALL |
| 202R | 20 | HQ | P | | 0-0 | 73-21-13 | D06382P | 16 | | | D08334J | 16 | | | ALL |
| 202Z | | | P | | 0-0 | 73-21-13 | D06382P | = CC | M | | D08334J | = CC | M | | ALL |
| 203B | 20 | HQ | R | | 5-1 | 73-21-14 | SP03114 | 8 | | | D08334J | 6 | | | ALL |
| 203R | 20 | HQ | R | | 0-0 | 73-21-14 | SP03110 | 8 | | | D08334J | 5 | | | ALL |
| 203Z | | | R | | 0-0 | 73-21-14 | SP03110 | REF | V | | D08334J | = CC | M | | ALL |
| 204B | 20 | HQ | S | | 16-9 | 73-21-14 | D06382P | 24 | | | D08334J | 24 | | | ALL |
| 204R | 20 | HQ | S | | 0-0 | 73-21-14 | D06382P | 23 | | | D08334J | 23 | | | ALL |
| 204Z | | | S | | 0-0 | 73-21-14 | D06382P | = CC | M | | D08334J | = CC | M | | ALL |
| 205B | 20 | HQ | IE | | 16-9 | 77-12-11 | D08334J | 3 | | | D06382P | 3 | | | ALL |
| 205R | 20 | HQ | IE | | 0-0 | 77-12-11 | D08334J | 2 | | | D06382P | 2 | | | ALL |
| 205Z | | | IE | | 0-0 | 77-12-11 | D08334J | = CC | M | | D06382P | = CC | M | | ALL |
| 208B | 20 | HQ | K | | 13-4 | 73-21-14 | D06382P | 6 | | | SP03114 | | 8 | | ALL |
| 208R | 20 | HQ | K | | 0-0 | 73-21-14 | D06382P | 5 | | | SP03110 | | 8 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0390
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0392 | 286T0392 | | | R. STRUT-R2-EEC-N1 ANALOG (continued) | | | | | | | | | | | | |
| 208Z | | | K | 0-0 | 73-21-14 | D06382P | = CC | M | | SP03110 | REF | V | | ALL | | |
| 210B | 20 | HQ | M | 4-7 | 73-21-14 | SP03106 | | 8 | | D08334J | 33 | | | ALL | | |
| 210R | 20 | HQ | M | 0-0 | 73-21-14 | SP03102 | | 8 | | D08334J | 32 | | | ALL | | |
| 210Z | | | M | 0-0 | 73-21-14 | SP03102 | REF | V | | D08334J | = CC | M | | ALL | | |
| 215B | 20 | HQ | IO | 16-9 | 73-21-17 | D06382P | | 28 | | D06382P | 28 | | | ALL | | |
| 215R | 20 | HQ | IO | 0-0 | 73-21-12 | D08334J | | 17 | | D06382P | 17 | | | ALL | | |
| 215Z | | | IO | 0-0 | 73-21-12 | D08334J | = CC | M | | D06382P | = CC | M | | 050-099, 155-199, 277-299 | | |
| 215Z | | | IO | 0-0 | 73-21-17 | D08334J | = CC | M | | D06382P | = CC | M | | 150-154, 275-276 | | |
| 222B | 20 | HQ | IV | 4-7 | 73-21-14 | D08334J | | 37 | | SP03208 | | 8 | | ALL | | |
| 222R | 20 | HQ | IV | 0-0 | 73-21-14 | D08334J | | 36 | | SP03204 | | 8 | | ALL | | |
| 222Z | | | IV | 0-0 | 73-21-14 | D08334J | = CC | M | | SP03204 | REF | V | | ALL | | |
| 223B | 20 | HQ | IW | 13-11 | 73-21-14 | D06382P | | 8 | | SP03208 | | 8 | | ALL | | |
| 223R | 20 | HQ | IW | 0-0 | 73-21-14 | D06382P | | 7 | | SP03204 | | 8 | | ALL | | |
| 223Z | | | IW | 0-0 | 73-21-14 | D06382P | = CC | M | | SP03204 | REF | V | | ALL | | |
| 224B | 20 | HQ | IX | 4-7 | 78-36-21 | D08334J | | 30 | | SP09599 | | 8 | | ALL | | |
| 224R | 20 | HQ | IX | 0-0 | 78-36-21 | D08334J | | 29 | | SP09601 | | 8 | | ALL | | |
| 224Z | | | IX | 0-0 | 78-36-21 | D08334J | = CC | M | | SP09599 | REF | V | | ALL | | |
| 225B | 20 | HQ | IY | 16-9 | 73-21-11 | D06382P | | 10 | | D08334J | 40 | | | ALL | | |
| 225R | 20 | HQ | IY | 0-0 | 73-21-11 | D06382P | | 19 | | D08334J | 39 | | | ALL | | |
| 225Z | | | IY | 0-0 | 73-21-11 | D06382P | = CC | M | | D08334J | = CC | M | | ALL | | |
| 242B | 20 | HQ | JQ | 3-0 | 73-21-14 | D08334J | | 12 | | SM00005 | | VH | | 050-099 | | |
| 242B | 20 | HQ | JQ | 3-0 | 73-21-14 | D08334J | | 12 | | SM00005 | | 8 | | 150-199, 275-299 | | |
| 242R | 20 | HQ | JQ | 0-0 | 73-21-14 | D08334J | | 21 | | SM00005 | | VH | | 050-099 | | |
| 242R | 20 | HQ | JQ | 0-0 | 73-21-14 | D08334J | | 21 | | SM00005 | | 8 | | 150-199, 275-299 | | |
| 242Z | | | JQ | 0-0 | 73-21-14 | D08334J | = CC | M | | SM00005 | REF | VH | | 050-099 | | |
| 242Z | | | JQ | 0-0 | 73-21-14 | D08334J | = CC | M | | SM00005 | REF | V | | 150-199, 275-299 | | |
| 243B | 20 | HQ | JR | 3-0 | 73-21-14 | D08334J | | 20 | | SM00005 | | 8 | | 150-152, 154-199, 275-299 | | |
| 243R | 20 | HQ | JR | 0-0 | 73-21-14 | D08334J | | 14 | | SM00005 | | 8 | | 150-152, 154-199, 275-299 | | |
| 243Z | | | JR | 0-0 | 73-21-14 | D08334J | = CC | M | | SM00005 | REF | V | | 150-152, 154-199, 275-299 | | |
| 301B | 20 | HR | Q | 16-9 | 73-21-13 | D06382P | | 27 | | D08334J | 27 | | | ALL | | |
| 301R | 20 | HR | Q | 0-0 | 73-21-13 | D06382P | | 26 | | D08334J | 26 | | | ALL | | |
| 301Y | 20 | HR | Q | 0-0 | 73-21-13 | D06382P | | 25 | | D08334J | 25 | | | ALL | | |
| 301Z | | | Q | 0-0 | 73-21-13 | D06382P | = CC | M | | D08334J | = CC | M | | ALL | | |
| 306B | 20 | HR | JR | 3-0 | 73-21-14 | D08334J | | 20 | | SM00005 | | VH | | 050-099 | | |
| 306B | 20 | HR | AO | 4-0 | 73-21-14 | D08334J | | 20 | | SM00005 | | 8 | | 153 | | |

WIRE LIST

D280T132

91-21-11

Section W0390

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0392 | 286T0392 | | | R. STRUT-R2-EEC-N1 ANALOG (continued) | | | | | | | | | | | |
| 306R | 20 | HR | JR | 0-0 | 73-21-14 | D08334J | 14 | | | | SM00005 | | VH | | 050-099 |
| 306R | 20 | HR | A0 | 0-0 | 73-21-14 | D08334J | 14 | | | | SM00005 | | 8 | | 153 |
| 306Y | 20 | HR | JR | 0-0 | 73-21-14 | D08334J | 41 | | | | SM00005 | | VH | | 050-099 |
| 306Y | 20 | HR | A0 | 0-0 | 73-21-14 | D08334J | 41 | | | | SM00005 | | 8 | | 153 |
| 306Z | | | JR | 0-0 | 73-21-14 | D08334J | = CC | M | | | SM00005 | REF | VH | | 050-099 |
| 306Z | | | A0 | 0-0 | 73-21-14 | D08334J | = CC | M | | | SM00005 | | 8 | | 153 |
| W0394 | 286T0394 | | | R SAILBOAT-R2-HYDRAULICS | | | | | | | | | | | |
| 001 | 18 | HL | | 7-0 | 78-34-21 | GD04682 | D.. | N | | | D02120 | | 1 | | ALL |
| 002 | 18 | HL | | 9-0 | 78-34-21 | D04170J | 2 | | | | D02120 | CAP | Y | | ALL |
| 003 | 18 | HL | | 9-0 | 78-34-21 | D04170J | 3 | | | | D02120 | | 3 | | ALL |
| 004 | 18 | HL | | 6-0 | 29-32-11 | D04170J | 9 | | | | D00500 | | 1 | | ALL |
| 006 | 18 | HL | | 5-0 | 29-32-11 | D00500 | 2 | | | | GD02392 | D.. | N | | ALL |
| 007 | 18 | HL | | 8-0 | 29-32-11 | D04170J | 5 | | | | GD02392 | D.. | N | | ALL |
| 008 | 18 | HL | | 9-0 | 78-36-21 | D04170J | 6 | | | | D02138 | | 1 | | ALL |
| 009 | 18 | HL | | 6-0 | 78-36-21 | GD02392 | D.. | N | | | D02138 | | 2 | | ALL |
| 010 | 18 | HL | | 9-0 | SPARE | D04170J | 8 | | | | D02138 | CAP | Y | | ALL |
| 011 | 20 | HP | A | 7-0 | 29-33-11 | D04170J | 12 | | | | D00060 | | 7 | | ALL |
| 011Z | | | A | 0-0 | 29-33-11 | D04170J | | | | FB | D00060 | | | FA | ALL |
| 012 | 18 | HL | | 7-0 | 29-33-11 | D04170J | 14 | | | | D00060 | | 5 | | ALL |
| 013 | 18 | HL | | 7-0 | 29-33-11 | D04170J | 15 | | | | D00060 | | 3 | | ALL |
| 014 | 18 | HL | | 7-0 | 29-33-11 | D04170J | 10 | | | | D00060 | | 4 | | ALL |
| 015 | 18 | HL | | 5-0 | 29-33-11 | GD02394 | S.. | N | | | D00060 | | 2 | | ALL |
| 018 | 18 | HL | | 5-0 | 29-11-21 | GD02390 | D.. | N | | | D00496 | | E | | ALL |
| 019 | 18 | HL | | 5-0 | 29-32-11 | D00048 | 2 | | | | GD02392 | D.. | N | | ALL |
| 020 | 18 | HL | | 8-0 | 29-32-11 | D04170J | 16 | | | | D00048 | | 1 | | ALL |
| 021 | 18 | HL | | 6-0 | 29-11-22 | D00074 | 2 | | | | GD02390 | D.. | N | | ALL |
| 022 | 18 | HL | | 8-0 | 29-11-22 | D00074 | 3 | | | | D04170J | | 17 | | ALL |
| 026 | 18 | HL | | 5-0 | 29-32-11 | D00048 | 3 | | | | GD02394 | S.. | N | | ALL |
| 027 | 18 | HL | | 6-0 | 29-32-11 | D00500 | 3 | | | | GD02394 | S.. | N | | ALL |
| 081 | 18 | HL | | 11-0 | 78-36-21 | D20126 | 1 | | | | D04170J | | 19 | | ALL |
| 082 | 18 | HL | | 9-0 | 78-36-21 | D20126 | 2 | | | | GD04682 | D.. | N | | ALL |
| 083 | 18 | HL | | 11-0 | 78-36-21 | D20126 | 3 | | | | D04170J | | 18 | | ALL |
| 100 | 18 | HL | | 8-0 | 78-34-21 | GD04682 | D.. | N | | | D20120 | | 1 | | ALL |
| 101 | 18 | HL | | 5-0 | 78-34-21 | GD02394 | S.. | N | | | D04170J | | | FD | ALL |
| 102 | 18 | HP | C | 10-0 | 78-34-21 | D20120 | 3 | | | | D04170J | | 1 | | ALL |
| 102Z | | | C | 0-0 | 78-34-21 | D20120 | DED | | | | D04170J | | | FD | ALL |
| 103 | 18 | HP | D | 10-0 | 78-34-21 | D20120 | 2 | | | | D04170J | | 7 | | ALL |
| 103Z | | | D | 0-0 | 78-34-21 | D20120 | DED | | | | D04170J | | | FD | ALL |

WIRE LIST

D280T132

91-21-11
Section W0390
Page 6
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0394 | 286T0394 | | | R SAILBOAT-R2-HYDRAULICS (continued) | | | | | | | | | | | | |
| 201B | 20 | HQ | B | 7-0 | 29-11-21 | D04406J | | 1 | | | | D00496 | A | | ALL | |
| 201R | 20 | HQ | B | 0-0 | 29-11-21 | D04406J | | 2 | | | | D00496 | B | | ALL | |
| 201Z | | | B | 0-0 | 29-11-21 | D04406J | | DED | | | | D00496 | DED | | ALL | |
| FRA | | | | 0-0 | 29-33-11 | D00060 | | | | FA | | D00060 | 1 | | ALL | |
| FRB | | | | 0-0 | 29-33-11 | D00060 | | | | FA | | D00060 | 6 | | ALL | |
| FRC | | | | 0-0 | 29-33-11 | D04170J | | | | FB | | D04170J | 4 | | ALL | |
| FRD | | | | 0-0 | 29-33-11 | D04170J | | | | FB | | D04170J | 11 | | ALL | |
| FRE | | | | 0-0 | 29-33-11 | D04170J | | | | FB | | D04170J | 13 | | ALL | |
| W0396 | 286T0396 | | | L. STRUT-L2-EEC-N1 ANALOG | | | | | | | | | | | | |
| 001 | 18 | HL | | 14-0 | 30-34-11 | D06384P | | 1 | | | | D08320J | 1 | | ALL | |
| 002 | 16 | HP | A | 14-0 | 73-21-20 | D06384P | | 13 | | | | D08320J | 13 | | ALL | |
| 002Z | | | A | 0-0 | 73-21-20 | D06384P | | =CC | M | | | D08320J | =CC | M | ALL | |
| 003 | 16 | HP | AC | 6-0 | 73-21-11 | SP03096 | | 8 | | | | D08320J | 4 | | ALL | |
| 003Z | | | AC | 0-0 | 73-21-11 | SP03096 | | REF | V | | | D08320J | =CC | M | ALL | |
| 010 | 20 | HP | AA | 4-0 | 73-21-14 | D08320J | | 41 | | | | SM00008 | VH | | 050-099 | |
| 010 | 18 | HL | | 1-0 | 73-21-14 | D08320J | | 12 | | | | D08320J | 14 | | 150-152, 154-199, 275-299 | |
| 010 | 20 | HP | A1 | 4-0 | 73-21-14 | D08320J | | 41 | | | | SM00008 | VH | | 153 | |
| 010Z | | | AA | 0-0 | 73-21-14 | D08320J | | =CC | M | | | SM00008 | REF | VH | 050-099 | |
| 010Z | | | A1 | 0-0 | 73-21-14 | D08320J | | =CC | M | | | SM00008 | VH | | 153 | |
| 014 | 20 | HP | AN | 6-0 | 73-21-11 | SP03080 | | 8 | | | | D08320J | 8 | | ALL | |
| 014Z | | | AN | 0-0 | 73-21-11 | SP03080 | | REF | V | | | D08320J | =CC | M | ALL | |
| 025 | 16 | HP | J | 14-0 | SPARE | D06384P | | 22 | | | | D08320J | 35 | | ALL | |
| 025Z | | | J | 0-0 | SPARE | D06384P | | =CC | M | | | D08320J | =CC | M | ALL | |
| 100 | 20 | HP | AD | 5-0 | 73-21-17 | D08320J | | 42 | | | | SP03478 | 8 | | ALL | |
| 100Z | | | AD | 0-0 | 73-21-17 | D08320J | | =CC | M | | | SP03478 | REF | V | ALL | |
| 101 | 20 | HP | EA | 6-0 | 78-36-11 | D08320J | | 34 | | | | SP09579 | 8 | | ALL | |
| 101Z | | | EA | 0-0 | 78-36-11 | D08320J | | =CC | M | | | SP09579 | REF | V | ALL | |
| 102 | 20 | HP | EB | 6-0 | 78-36-11 | D08320J | | 31 | | | | SP09581 | 8 | | ALL | |
| 102Z | | | EB | 0-0 | 78-36-11 | D08320J | | =CC | M | | | SP09581 | REF | V | ALL | |
| 103 | 20 | HP | EC | 6-0 | 73-21-14 | D08320J | | 9 | | | | SP03124 | 8 | | ALL | |
| 103Z | | | EC | 0-0 | 73-21-14 | D08320J | | =CC | M | | | SP03124 | REF | V | ALL | |
| 107 | 20 | HP | EG | 6-0 | 73-21-19 | SP03092 | | 8 | | | | D08320J | 18 | | ALL | |
| 107Z | | | EG | 0-0 | 73-21-19 | SP03092 | | REF | V | | | D08320J | =CC | M | ALL | |
| 109 | 20 | HP | ED | 11-0 | 73-21-14 | D06384P | | 11 | | | | SP03124 | 8 | | ALL | |
| 109Z | | | ED | 0-0 | 73-21-14 | D06384P | | =CC | M | | | SP03124 | REF | V | ALL | |
| 111 | 20 | HP | IF | 6-0 | 73-21-11 | SP03076 | | 8 | | | | D08320J | 7 | | ALL | |
| 111Z | | | IF | 0-0 | 73-21-11 | SP03076 | | REF | V | | | D08320J | =CC | M | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0390

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0396 | 286T0396 | | | L. STRUT-L2-EEC-N1 ANALOG (continued) | | | | | | | | | | | | |
| 132 | 20 | HP | FG | 5-0 | 78-36-11 | SP03340 | | 8 | | D08320J | 19 | | | ALL | | |
| 132Z | | | FG | 0-0 | 78-36-11 | SP03340 | REF | V | | D08320J | = CC | M | | ALL | | |
| 201B | 20 | HQ | IA | 14-0 | 31-35-14 | D06384P | | 21 | | D08320J | 11 | | | 050-099, 155-199, 278-299 | | |
| 201B | 20 | HQ | IA | 14-0 | 31-35-14 | D08320J | | 11 | | D06384P | 21 | | | 150-154, 275-276 | | |
| 201R | 20 | HQ | IA | 0-0 | 31-35-14 | D06384P | | 20 | | D08320J | 10 | | | 050-099, 155-199, 278-299 | | |
| 201R | 20 | HQ | IA | 0-0 | 31-35-14 | D08320J | | 10 | | D06384P | 20 | | | 150-154, 275-276 | | |
| 201Z | | | IA | 0-0 | 31-35-14 | D06384P | = CC | M | | D08320J | = CC | M | | 050-099, 155-199, 278-299 | | |
| 201Z | | | IA | 0-0 | 31-35-14 | D08320J | = CC | M | | D06384P | = CC | M | | 150-154, 275-276 | | |
| 202B | 20 | HQ | S | 14-0 | 73-21-13 | D06384P | | 15 | | D08320J | 15 | | | ALL | | |
| 202R | 20 | HQ | S | 0-0 | 73-21-13 | D06384P | | 16 | | D08320J | 16 | | | ALL | | |
| 202Z | | | S | 0-0 | 73-21-13 | D06384P | = CC | M | | D08320J | = CC | M | | ALL | | |
| 203B | 20 | HQ | R | 6-0 | 73-21-14 | SP03090 | | 8 | | D08320J | 6 | | | ALL | | |
| 203R | 20 | HQ | R | 0-0 | 73-21-14 | SP03086 | | 8 | | D08320J | 5 | | | ALL | | |
| 203Z | | | R | 0-0 | 73-21-14 | SP03086 | REF | V | | D08320J | = CC | M | | ALL | | |
| 204B | 20 | HQ | U | 14-0 | 73-21-14 | D06384P | | 24 | | D08320J | 24 | | | ALL | | |
| 204R | 20 | HQ | U | 0-0 | 73-21-14 | D06384P | | 23 | | D08320J | 23 | | | ALL | | |
| 204Z | | | U | 0-0 | 73-21-14 | D06384P | = CC | M | | D08320J | = CC | M | | ALL | | |
| 205B | 20 | HQ | IE | 14-0 | 77-12-11 | D08320J | | 3 | | D06384P | 3 | | | ALL | | |
| 205R | 20 | HQ | IE | 0-0 | 77-12-11 | D08320J | | 2 | | D06384P | 2 | | | ALL | | |
| 205Z | | | IE | 0-0 | 77-12-11 | D08320J | = CC | M | | D06384P | = CC | M | | ALL | | |
| 208B | 20 | HQ | K | 11-0 | 73-21-14 | D06384P | | 6 | | SP03090 | 8 | | | ALL | | |
| 208R | 20 | HQ | K | 0-0 | 73-21-14 | D06384P | | 5 | | SP03086 | 8 | | | ALL | | |
| 208Z | | | K | 0-0 | 73-21-14 | D06384P | = CC | M | | SP03086 | REF | V | | ALL | | |
| 210B | 20 | HQ | M | 6-0 | 73-21-14 | SP03082 | | 8 | | D08320J | 33 | | | ALL | | |
| 210R | 20 | HQ | M | 0-0 | 73-21-14 | SP03078 | | 8 | | D08320J | 32 | | | ALL | | |
| 210Z | | | M | 0-0 | 73-21-14 | SP03078 | REF | V | | D08320J | = CC | M | | ALL | | |
| 215B | 20 | HQ | IO | 14-0 | 73-21-17 | D08320J | | 28 | | D06384P | 28 | | | ALL | | |
| 215R | 20 | HQ | IO | 0-0 | 73-21-12 | D08320J | | 17 | | D06384P | 17 | | | ALL | | |
| 215Z | | | IO | 0-0 | 73-21-12 | D08320J | = CC | M | | D06384P | = CC | M | | 050-099, 155-199, 277-299 | | |
| 215Z | | | IO | 0-0 | 73-21-17 | D08320J | = CC | M | | D06384P | = CC | M | | 150-154, 275-276 | | |
| 222B | 20 | HQ | IV | 6-0 | 73-21-14 | D08320J | | 37 | | SP03198 | 8 | | | ALL | | |
| 222R | 20 | HQ | IV | 0-0 | 73-21-14 | D08320J | | 36 | | SP03196 | 8 | | | ALL | | |
| 222Z | | | IV | 0-0 | 73-21-14 | D08320J | = CC | M | | SP03196 | REF | V | | ALL | | |
| 223B | 20 | HQ | IW | 11-0 | 73-21-14 | D06384P | | 8 | | SP03198 | 8 | | | ALL | | |
| 223R | 20 | HQ | IW | 0-0 | 73-21-14 | D06384P | | 7 | | SP03196 | 8 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0390

Page 8

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0396 | 286T0396 | | | L. STRUT-L2-EEC-N1 ANALOG (continued) | | | | | | | | | | | |
| 223Z | | | IW | 0-0 | 73-21-14 | D06384P | = CC | M | | SP03196 | REF | V | | ALL | |
| 224B | 20 | HQ | IX | 6-0 | 78-36-11 | D08320J | | 30 | | SP09583 | | 8 | | ALL | |
| 224R | 20 | HQ | IX | 0-0 | 78-36-11 | D08320J | | 29 | | SP09585 | | 8 | | ALL | |
| 224Z | | | IX | 0-0 | 78-36-11 | D08320J | = CC | M | | SP09583 | REF | V | | ALL | |
| 225B | 20 | HQ | IY | 14-0 | 73-21-11 | D06384P | | 10 | | D08320J | | 40 | | ALL | |
| 225R | 20 | HQ | IY | 0-0 | 73-21-11 | D06384P | | 19 | | D08320J | | 39 | | ALL | |
| 225Z | | | IY | 0-0 | 73-21-11 | D06384P | = CC | M | | D08320J | = CC | M | | ALL | |
| 230B | 20 | HQ | JA | 4-0 | 73-21-14 | D08320J | | 12 | | SM00008 | | VH | | 050-099 | |
| 230B | 20 | HQ | A0 | 4-0 | 73-21-14 | D08320J | | 12 | | SM00008 | | VH | | 153 | |
| 230R | 20 | HQ | JA | 0-0 | 73-21-14 | D08320J | | 14 | | SM00008 | | VH | | 050-099 | |
| 230R | 20 | HQ | A0 | 0-0 | 73-21-14 | D08320J | | 14 | | SM00008 | | VH | | 153 | |
| 230Z | | | JA | 0-0 | 73-21-14 | D08320J | = CC | M | | SM00008 | REF | VH | | 050-099 | |
| 230Z | | | A0 | 0-0 | 73-21-14 | D08320J | = CC | M | | SM00008 | | VH | | 153 | |
| 301B | 20 | HR | Y | 14-0 | 73-21-13 | D06384P | | 27 | | D08320J | | 27 | | ALL | |
| 301R | 20 | HR | Y | 0-0 | 73-21-13 | D06384P | | 26 | | D08320J | | 26 | | ALL | |
| 301Y | 20 | HR | Y | 0-0 | 73-21-13 | D06384P | | 25 | | D08320J | | 25 | | ALL | |
| 301Z | | | Y | 0-0 | 73-21-13 | D06384P | = CC | M | | D08320J | = CC | M | | ALL | |
| W0397 | 286T0397 | | | AFDS WARN & ANN L,P1 TO SHELF | | | | | | | | | | | |
| 001 | 24 | PK | | 22-0 | 34-22-17 | D05581J | | 6 | | D04167J | | 6 | | ALL | |
| 002 | 24 | PK | | 22-0 | 34-22-17 | D05581J | | 2 | | D04167J | | 2 | | ALL | |
| 003 | 24 | PK | | 22-0 | 34-22-17 | D05581J | | 3 | | D04167J | | 3 | | ALL | |
| 004 | 24 | PK | | 22-0 | 34-22-17 | D05581J | | 4 | | D04167J | | 4 | | ALL | |
| 005 | 22 | PA | | 23-0 | 22-14-11 | D04169J | | 5 | | D04167J | | 5 | | ALL | |
| 006 | 24 | PK | | 23-0 | 34-22-37 | D04901J | | 1 | | D04167J | | 1 | | ALL | |
| 009 | 22 | PA | | 23-0 | 34-45-14 | D04169J | | 1 | | D04167J | | 35 | | ALL | |
| 016 | 24 | PK | | 23-0 | 32-42-11 | D04167J | | 44 | | D04169J | | 24 | | ALL | |
| 018 | 22 | PA | | 12-0 | 34-22-81 | D04167J | | 30 | | SP00373 | | 9 | | ALL | |
| 019 | 24 | PK | | 25-0 | 31-31-26 | D04171J | | 17 | | D05523J | | 10 | | ALL | |
| 020 | 22 | PA | | 23-0 | 34-45-14 | D04169J | | 35 | | D04171J | | 22 | | 050-099, 150-152, 155-199, 277-299 | |
| 020 | 22 | PA | | 23-0 | 34-45-14 | D04167J | | 31 | | D04169J | | 35 | | 153-154 | |
| 021 | 22 | PA | | 23-0 | SPARE | D04169J | | 39 | | D04171J | | 23 | | 050-099, 155-199, 277-299 | |
| 021 | 22 | PA | | 23-0 | 34-45-14 | D04169J | | 39 | | D04171J | | 23 | | 150-152 | |
| 021 | 22 | PA | | 23-0 | 34-45-14 | D04167J | | 53 | | D04169J | | 39 | | 153-154 | |
| 022 | 24 | PK | | 22-0 | 34-22-17 | D04167J | | 42 | | D05581J | | 22 | | ALL | |
| 023 | 22 | PA | | 24-0 | SPARE | D04171J | | 3 | | D04901J | | 3 | | ALL | |
| 024 | 22 | PA | | 24-0 | SPARE | D04171J | | 4 | | D04901J | | 4 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0390

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|---------|-------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0397 | 286T0397 | | | AFDS WARN & ANN L,P1 TO SHELF (continued) | | | | | | | | | | | |
| 026 | 24 | | PK | 23-0 | 22-13-11 | D04167J | | 16 | | D04169J | | 16 | | | ALL |
| 027 | 24 | | PK | 24-0 | 22-14-11 | D04167J | | 47 | | D05523J | | 7 | | | ALL |
| 028 | 24 | | PK | 24-0 | 22-14-11 | D04167J | | 48 | | D05523J | | 8 | | | ALL |
| 029 | 24 | | PK | 24-0 | 22-14-11 | D04167J | | 49 | | D05523J | | 9 | | | ALL |
| 030 | 22 | | PA | 22-0 | 34-22-16 | D05581J | | 23 | | D04167J | | 43 | | | ALL |
| 031 | 24 | | PK | 23-0 | 22-41-13 | D04167J | | 51 | | D04169J | | 15 | | | ALL |
| 032 | 24 | | PK | 23-0 | 22-41-13 | D04901J | | 2 | | D04167J | | 52 | | | ALL |
| 033 | 24 | | PK | 23-0 | 22-41-13 | D04169J | | 30 | | D04167J | | 50 | | | ALL |
| 043 | 24 | | PK | 25-0 | 34-46-12 | D04171J | | 13 | | D05523J | | 13 | | | ALL |
| 045 | 24 | | PK | 25-0 | 34-46-12 | D04171J | | 15 | | D05523J | | 15 | | | ALL |
| 046 | 24 | | PK | 25-0 | SPARE | D04171J | | 16 | | D05523J | | 16 | | | 050-099 |
| 048 | 24 | | PK | 5-0 | 34-46-12 | D05523J | | 18 | | D04169J | | 8 | | | ALL |
| 050 | 24 | | PK | 5-0 | SPARE | D04169J | | 7 | | D05523J | | 17 | | | ALL |
| 051 | 24 | | PK | 23-0 | SPARE | D04169J | | 9 | | D04171J | | 9 | | | 050-099, 277-299 |
| 051 | 24 | | PK | 24-0 | SPARE | D04169J | | 9 | | D04171J | | 9 | | | 150-199, 275-276 |
| 052 | 24 | | PK | 25-0 | SPARE | D04171J | | 2 | | D05523J | | 2 | | | ALL |
| 053 | 24 | | PK | 23-0 | SPARE | D04167J | | 45 | | D04901J | | 5 | | | ALL |
| 054 | 24 | | PK | 22-0 | SPARE | D04167J | | 46 | | D05581J | | 20 | | | ALL |
| 055 | 24 | | PK | 22-0 | SPARE | D04167J | | 55 | | D05581J | | 21 | | | ALL |
| 058 | 22 | | PA | 23-0 | 22-34-11 | D04167J | | 54 | | D04169J | | 10 | | | ALL |
| 202 | 20 | | UA | 1-6 | 34-22-81 | GD00401 | | S.. | 2 | D04167J | | | | FC | 050-099, 150-156, 162-166, 280-299 |
| 202 | 20 | | UA | 1-6 | SPARE | GD00401 | | S.. | 2 | D04167J | | | | FC | 275-276 |
| 202B | 24 | | PW | IB | 22-0 | 34-22-81 | D05581J | | 11 | D04167J | | 11 | | | 050-099, 150-156, 162-166, 280-299 |
| 202B | 24 | | PW | IB | 22-0 | SPARE | D05581J | | 11 | D04167J | | 11 | | | 275-276 |
| 202R | 24 | | PW | IB | 0-0 | 34-22-81 | D05581J | | 10 | D04167J | | 10 | | | 050-099, 150-156, 162-166, 280-299 |
| 202R | 24 | | PW | IB | 0-0 | SPARE | D05581J | | 10 | D04167J | | 10 | | | 275-276 |
| 202Z | | | | IB | 0-0 | 34-22-81 | D05581J | | 12 | D04167J | | | | FC | 050-099, 150-156, 162-166, 280-299 |
| 202Z | | | | IB | 0-0 | SPARE | D05581J | | 12 | D04167J | | | | FC | 275-276 |
| 203 | 20 | | UA | 1-6 | 34-22-81 | GD00401 | | S.. | 2 | D04167J | | | | FD | ALL |
| 203B | 24 | | PW | IC | 22-0 | 34-22-81 | D05581J | | 14 | D04167J | | 14 | | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 34-22-81 | D05581J | | 13 | D04167J | | 13 | | | ALL |
| 203Z | | | | IC | 0-0 | 34-22-81 | D05581J | | 15 | D04167J | | | | FD | ALL |
| 205 | 20 | | UA | 1-6 | 34-13-11 | GD00401 | | S.. | 2 | D04167J | | | | FA | ALL |
| 205B | 24 | | PW | IE | 23-0 | 34-13-11 | D04169J | | 22 | D04167J | | 22 | | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 34-13-11 | D04169J | | 21 | D04167J | | 21 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0390

Page 10

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0397 | 286T0397 | | | AFDS WARN & ANN L,P1 TO SHELF (continued) | | | | | | | | | | | |
| 205Z | | | | IE | 0-0 | 34-13-11 | D04169J | 23 | | | D04167J | | | FA | ALL |
| 206B | 24 | PW | | IF | 24-0 | SPARE | D05523J | 5 | | | D04167J | 25 | | | ALL |
| 206R | 24 | PW | | IF | 0-0 | SPARE | D05523J | 4 | | | D04167J | 24 | | | ALL |
| 206Z | | | | IF | 0-0 | SPARE | D05523J | 6 | | | D04167J | 26 | | | ALL |
| 207 | 20 | UA | | | 1-6 | 34-22-82 | D04167J | | | FE | GD00401 | S.. | 2 | | ALL |
| 207B | 24 | PW | | IG | 22-0 | 34-22-82 | D05581J | 8 | | | D04167J | 28 | | | ALL |
| 207R | 24 | PW | | IG | 0-0 | 34-22-82 | D05581J | 7 | | | D04167J | 27 | | | ALL |
| 207Z | | | | IG | 0-0 | 34-22-82 | D05581J | 9 | | | D04167J | | | FE | ALL |
| 209B | 22 | PR | | II | 23-0 | SPARE | D04169J | 3 | | | D04167J | 33 | | | ALL |
| 209R | 22 | PR | | II | 0-0 | SPARE | D04169J | 2 | | | D04167J | 32 | | | ALL |
| 209Z | | | | II | 0-0 | SPARE | D04169J | 4 | | | D04167J | 34 | | | ALL |
| 210B | 20 | PR | | IJ | 23-0 | 34-12-11 | D04169J | 13 | | | D04167J | 40 | | | ALL |
| 210R | 20 | PR | | IJ | 0-0 | 34-12-11 | D04169J | 12 | | | D04167J | 39 | | | ALL |
| 210Z | | | | IJ | 0-0 | 34-12-11 | D04169J | 14 | | | D04167J | 41 | | | ALL |
| 211 | 20 | UA | | | 1-6 | 34-22-91 | GD00401 | S.. | 2 | | D04171J | | | IK | ALL |
| 211B | 24 | PW | | IK | 25-0 | 34-22-91 | D04171J | 20 | | | D05523J | 20 | | | ALL |
| 211R | 24 | PW | | IK | 0-0 | 34-22-91 | D04171J | 19 | | | D05523J | 19 | | | ALL |
| 211Z | | | | IK | 0-0 | 34-22-91 | D04171J | | | IK | D05523J | 21 | | | ALL |
| 212B | 24 | PW | | IL | 23-0 | SPARE | D04167J | 8 | | | D04169J | 33 | | | 153-154 |
| 212R | 24 | PW | | IL | 0-0 | SPARE | D04167J | 7 | | | D04169J | 32 | | | 153-154 |
| 212Z | | | | IL | 0-0 | SPARE | D04167J | 9 | | | D04169J | 34 | | | 153-154 |
| 215 | 20 | UA | | | 1-6 | 34-13-21 | D04171J | | | IO | GD00401 | S.. | 2 | | ALL |
| 215B | 24 | PW | | IO | 23-0 | 34-13-21 | D04171J | 6 | | | D04169J | 26 | | | 050-099, 277-299 |
| 215B | 24 | PW | | IO | 24-0 | 34-13-21 | D04171J | 6 | | | D04169J | 26 | | | 150-199, 275-276 |
| 215R | 24 | PW | | IO | 0-0 | 34-13-21 | D04171J | 5 | | | D04169J | 25 | | | ALL |
| 215Z | | | | IO | 0-0 | 34-13-21 | D04171J | | | IO | D04169J | 27 | | | ALL |
| 301B | 24 | PM | | MA | 23-0 | 34-12-11 | D04169J | 19 | | | D04167J | 19 | | | ALL |
| 301R | 24 | PM | | MA | 0-0 | 34-12-11 | D04169J | 18 | | | D04167J | 18 | | | ALL |
| 301Y | 24 | PM | | MA | 0-0 | 34-12-11 | D04169J | 20 | | | D04167J | 20 | | | ALL |
| 302B | 24 | PM | | MB | 23-0 | SPARE | D04169J | 37 | | | D04167J | 37 | | | 150-199, 275-299 |
| 302R | 24 | PM | | MB | 0-0 | SPARE | D04169J | 36 | | | D04167J | 36 | | | 150-199, 275-299 |
| 302Y | 24 | PM | | MB | 0-0 | SPARE | D04169J | 38 | | | D04167J | 38 | | | 150-199, 275-299 |
| FRA | | | | | 0-0 | 34-13-11 | D04167J | | | FA | D04167J | 23 | | | ALL |
| FRC | | | | | 0-0 | 34-22-81 | D04167J | | | FC | D04167J | 12 | | | 050-099, 150-156, 162-166, 280-299 |
| FRC | | | | | 0-0 | SPARE | D04167J | | | FC | D04167J | 12 | | | 275-276 |
| FRD | | | | | 0-0 | 34-22-81 | D04167J | | | FD | D04167J | 15 | | | ALL |
| FRE | | | | | 0-0 | 34-22-82 | D04167J | | | FE | D04167J | 29 | | | ALL |
| FRG | | | | | 0-0 | 34-22-91 | D04171J | 21 | | | D04171J | | | IK | ALL |

WIRE LIST

D280T132

91-21-11

Section W0390

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0397 | 286T0397 | | | AFDS WARN & ANN L,P1 TO SHELF (continued) | | | | | | | | | | | |
| FRO | | | | | 0-0 | 34-13-21 | D04171J | | | | IO | D04171J | 7 | | ALL |
| W0398 | 286T0398 | | | L SAILBOAT-R2-HYDRAULICS | | | | | | | | | | | |
| 001 | 18 | | HL | | 8-0 | 29-11-12 | D04280J | | 1 | | | D00056 | 1 | | ALL |
| 002 | 18 | | HL | | 8-0 | 29-11-12 | D04280J | | 2 | | | D00056 | 3 | | ALL |
| 003 | 18 | | HL | | 5-0 | 29-11-12 | GD02410 | | D.. | N | | D00056 | 2 | | ALL |
| 006 | 18 | | HL | | 11-0 | 29-11-12 | D04280J | | 4 | | | D00052 | 3 | | ALL |
| 007 | 18 | | HL | | 8-0 | 29-11-12 | GD02410 | | D.. | N | | D00052 | 2 | | ALL |
| 011 | 18 | | HL | | 8-0 | 29-32-11 | D00916 | | 3 | | | SP02244 | 9 | | ALL |
| 201B | 18 | | HM | A | 10-0 | 29-11-12 | D00916 | | 1 | | | D04280J | 6 | | ALL |
| 201R | 18 | | HM | A | 0-0 | 29-11-12 | D00916 | | 2 | | | D04280J | 5 | | ALL |
| W0399 | 286T0399 | | | AFDS WARN & ANN C,P1 TO SHELF | | | | | | | | | | | |
| 001 | 24 | | PK | | 26-0 | SPARE | D04175J | | 4 | | | D04173J | 4 | | ALL |
| 012 | 24 | | PK | | 26-0 | SPARE | D04175J | | 12 | | | D04173J | 12 | | ALL |
| 014 | 22 | | PA | | 13-0 | 30-33-11 | SP02314 | | | 9 | | D04173J | 14 | | ALL |
| 017 | 24 | | PK | | 26-0 | 22-14-11 | D04175J | | 17 | | | D04173J | 17 | | ALL |
| 018 | 22 | | PA | | 26-0 | 22-14-11 | D04175J | | 13 | | | D04173J | 13 | | ALL |
| 019 | 24 | | PK | | 26-0 | 22-14-11 | D04175J | | 16 | | | D04173J | 16 | | ALL |
| 020 | 22 | | PA | | 26-0 | SPARE | D04175J | | 18 | | | D04173J | 18 | | ALL |
| 021 | 22 | | PA | | 26-0 | SPARE | D04175J | | 19 | | | D04173J | 19 | | ALL |
| 022 | 22 | | PA | | 26-0 | SPARE | D04175J | | 20 | | | D04173J | 20 | | ALL |
| 201 | 20 | | UA | | 1-6 | 34-22-81 | GD00401 | | S.. | 2 | | D04173J | | FA | ALL |
| 201B | 24 | | PW | IA | 26-0 | 34-22-81 | D04175J | | 7 | | | D04173J | 7 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-22-81 | D04175J | | 6 | | | D04173J | 6 | | ALL |
| 201Z | | | | IA | 0-0 | 34-22-81 | D04175J | | 8 | | | D04173J | | FA | ALL |
| 202 | 20 | | UA | | 1-6 | 34-22-82 | D04173J | | | | FB | GD00401 | S.. | 2 | ALL |
| 202B | 24 | | PW | IB | 26-0 | 34-22-82 | D04175J | | 2 | | | D04173J | 2 | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-22-82 | D04175J | | 1 | | | D04173J | 1 | | ALL |
| 202Z | | | | IB | 0-0 | 34-22-82 | D04175J | | 3 | | | D04173J | | FB | ALL |
| 203B | 20 | | PR | IC | 26-0 | SPARE | D04175J | | 10 | | | D04173J | 10 | | ALL |
| 203R | 20 | | PR | IC | 0-0 | SPARE | D04175J | | 9 | | | D04173J | 9 | | ALL |
| 203Z | | | | IC | 0-0 | SPARE | D04175J | | 11 | | | D04173J | 11 | | ALL |
| 204B | 24 | | PW | ID | 26-0 | SPARE | D04175J | | 21 | | | D04173J | 21 | | ALL |
| 204R | 24 | | PW | ID | 0-0 | SPARE | D04175J | | 22 | | | D04173J | 22 | | ALL |
| 204Z | | | | ID | 0-0 | SPARE | D04175J | | 23 | | | D04173J | 23 | | ALL |
| FRA | | | | | 0-0 | 34-22-81 | D04173J | | | | FA | D04173J | 8 | | ALL |
| FRB | | | | | 0-0 | 34-22-82 | D04173J | | | | FB | D04173J | 3 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0390
 Page 12 End
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0400 | 286T0400 | | | R SAILBOAT-L2-HYDRAULICS | | | | | | | | | | | |
| 001 | 18 | | HL | 7-0 | 29-11-22 | D04168J | | 1 | | | D00076 | | 1 | | ALL |
| 002 | 18 | | HL | 7-0 | 29-11-22 | D04168J | | 2 | | | D00076 | | 3 | | ALL |
| 003 | 18 | | HL | 4-0 | 29-11-22 | GD02404 | | | D.. | N | D00076 | | 2 | | ALL |
| 006 | 18 | | HL | 13-0 | 29-11-22 | D04168J | | 4 | | | D00072 | | 3 | | ALL |
| 007 | 18 | | HL | 9-0 | 29-11-22 | GD02404 | | | D.. | N | D00072 | | 2 | | ALL |
| 011 | 18 | | HL | 9-0 | 29-32-11 | D00922 | | 3 | | | SP02242 | | | 9 | ALL |
| 201B | 18 | | HM | A | 8-0 | 29-11-22 | D00922 | 1 | | | D04168J | | 6 | | ALL |
| 201R | 18 | | HM | A | 0-0 | 29-11-22 | D00922 | 2 | | | D04168J | | 7 | | ALL |
| W0401 | 286T0401 | | | LEFT FRONT SPAR SLAT #1 SWITCH | | | | | | | | | | | |
| 001 | 20 | | VF | A | 7-11 | 27-89-11 | D07546P | | | 2 | D03695 | | 1 | | 050-099, 151 |
| 001Z | | | | A | 0-0 | 27-89-11 | D07546P | | | DED | D03695 | | DED | | 050-099, 151 |
| 002 | 20 | | VF | B | 7-11 | 27-89-11 | D07546P | | | 1 | D03695 | | 2 | | 050-099, 151 |
| 002Z | | | | B | 0-0 | 27-89-11 | D07546P | | | DED | D03695 | | DED | | 050-099, 151 |
| W0402 | 286T0402 | | | R WING INBD FS-S2A-FUEL/FIRE DET/ENG INSTR | | | | | | | | | | | |
| 001 | 20 | | UA | | 23-3 | 80-11-11 | D04204J | | | 4 | D04634P | | 8 | | ALL |
| 002 | 20 | | VF | AB | 23-3 | 80-11-11 | D04204J | | | 5 | D04634P | | 7 | | ALL |
| 002Z | | | | AB | 0-0 | 80-11-11 | D04204J | | | =CC | D04634P | | =CC | L | ALL |
| 003 | 20 | | VF | AC | 23-3 | 80-11-11 | D04204J | | | 6 | D04634P | | 6 | | ALL |
| 003Z | | | | AC | 0-0 | 80-11-11 | D04204J | | | =CC | D04634P | | =CC | L | ALL |
| 004 | 20 | | UA | | 23-3 | 76-11-11 | D04204J | | | 8 | D04634P | | 12 | | ALL |
| 006 | 20 | | VF | AF | 23-3 | 76-11-11 | D04204J | | | 9 | D04634P | | 1 | | ALL |
| 006Z | | | | AF | 0-0 | 76-11-11 | D04204J | | | =CC | D04634P | | =CC | L | ALL |
| 007 | 20 | | UA | | 23-3 | SPARE | D04204J | | | 3 | D04634P | | 4 | | 050-099, 150-199 |
| 008 | 20 | | UA | | 23-3 | 76-11-11 | D04204J | | | 10 | D04634P | | 9 | | ALL |
| 011 | 20 | | UA | | 23-3 | SPARE | D04204J | | | 13 | D04634P | | 14 | | 150-199 |
| 012 | 20 | | UA | | 30-3 | 28-26-11 | D04444P | | | 7 | D04540P | | 7 | | ALL |
| 013 | 20 | | UA | | 30-3 | 28-26-11 | D04444P | | | 8 | D04540P | | 8 | | ALL |
| 014 | 20 | | UA | | 30-3 | 28-21-11 | D04444P | | | 9 | D04540P | | 9 | | ALL |
| 015 | 20 | | UA | | 30-3 | 28-21-13 | D04444P | | | 10 | D04540P | | 10 | | ALL |
| 016 | 20 | | UA | | 30-3 | 28-21-13 | D04444P | | | 11 | D04540P | | 11 | | ALL |
| 017 | 20 | | UA | | 30-3 | 28-21-11 | D04444P | | | 12 | D04540P | | 12 | | ALL |
| 018 | 20 | | UA | | 30-3 | 28-21-11 | D04444P | | | 13 | D04540P | | 13 | | ALL |
| 019 | 20 | | UA | | 30-3 | 28-21-11 | D04444P | | | 14 | D04540P | | 14 | | ALL |
| 020 | 20 | | UA | | 30-3 | 28-21-13 | D04444P | | | 15 | D04540P | | 15 | | ALL |
| 021 | 20 | | UA | | 30-3 | 28-21-13 | D04444P | | | 16 | D04540P | | 16 | | ALL |
| 022 | 20 | | UA | | 30-3 | 28-26-11 | D04444P | | | 17 | D04540P | | 17 | | ALL |
| 023 | 20 | | UA | | 30-3 | 28-26-11 | D04444P | | | 18 | D04540P | | 18 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0400

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0402 | 286T0402 | | | R WING INBD FS-S2A-FUEL/FIRE DET/ENG INSTR (continued) | | | | | | | | | | | |
| 024 | 20 | | UA | | 30-6 | 28-21-11 | D04442P | | | | D04540P | | 25 | | ALL |
| 025 | 20 | | UA | | 30-6 | 28-21-12 | D04442P | | | | D04540P | | 28 | | ALL |
| 026 | 20 | | UA | | 30-6 | 28-21-12 | D04442P | | | | D04540P | | 29 | | ALL |
| 027 | 20 | | UA | | 30-6 | 28-21-11 | D04442P | | | | D04540P | | 30 | | ALL |
| 028 | 20 | | UA | | 30-6 | 28-21-11 | D04442P | | | | D04540P | | 31 | | ALL |
| 029 | 18 | | UA | | 30-6 | 28-41-12 | D04442P | | | | D04540P | | 32 | DL | ALL |
| 030 | 20 | | UA | | 30-6 | 28-21-11 | D04442P | | | | D04540P | | 33 | | ALL |
| 031 | 20 | | UA | | 30-6 | 28-21-11 | D04442P | | | | D04540P | | 34 | | ALL |
| 032 | 20 | | UA | | 30-6 | 28-21-13 | D04442P | | | | D04540P | | 35 | | ALL |
| 033 | 20 | | UA | | 30-6 | 28-21-13 | D04442P | | | | D04540P | | 36 | | ALL |
| 036 | 20 | | UA | | 30-6 | 28-21-11 | D04442P | | | | D04540P | | 45 | | ALL |
| 037 | 20 | | UA | | 30-6 | 28-26-11 | D04442P | | | | D04540P | | 50 | | ALL |
| 039 | 20 | | UA | | 23-3 | SPARE | D04204J | | | | D04634P | | 11 | | 050-099, 150-199 |
| 040 | 20 | | UA | | 30-3 | 28-41-11 | D04444P | | | | D04540P | | 57 | | ALL |
| 041 | 20 | | UA | | 30-3 | 28-41-11 | D04444P | | | | D04540P | | 58 | | ALL |
| 042 | 20 | | VF | BQ | 23-3 | 76-11-11 | D04634P | | | | D04204J | | 12 | | 050-099 |
| 042 | 20 | | VF | BQ | 23-3 | 76-11-11 | D04204J | | | | D04634P | | 2 | | 150-199, 275-299 |
| 042Z | | | | BQ | 0-0 | 76-11-11 | D04634P | =CC | L | | D04204J | =CC | M | | 050-099 |
| 042Z | | | | BQ | 0-0 | 76-11-11 | D04204J | =CC | M | | D04634P | =CC | L | | 150-199, 275-299 |
| 043 | 20 | | UA | | 30-3 | 28-41-11 | D04540P | | | | D04444P | | 19 | | ALL |
| 044 | 20 | | UA | | 30-3 | 28-41-11 | D04540P | | | | D04444P | | 1 | | ALL |
| 053 | 18 | | UA | | 35-0 | 28-21-11 | D04540P | | | DL | D04444P | | 30 | | 050-099, 150-156, 162-166, 275-276 |
| 053 | 18 | | UA | | 30-3 | 28-21-11 | D04444P | | | | D04540P | | 51 | DL | 157, 167-199, 277-299 |
| 202B | 20 | | UB | B | 30-3 | 28-41-11 | D04444P | | | | D04540P | | 3 | | ALL |
| 202R | 20 | | UB | B | 0-0 | 28-41-11 | D04444P | | | | D04540P | | 4 | | ALL |
| 205B | 20 | | UB | E | 30-3 | 28-41-11 | D04444P | | | | D04540P | | 21 | | ALL |
| 205R | 20 | | UB | E | 0-0 | 28-41-11 | D04444P | | | | D04540P | | 22 | | ALL |
| 207B | 20 | | UB | G | 30-6 | SPARE | D04442P | | | | D04540P | | 26 | | ALL |
| 207R | 20 | | UB | G | 0-0 | SPARE | D04442P | | | | D04540P | | 27 | | ALL |
| 209B | 20 | | UB | J | 30-6 | 28-41-11 | D04442P | | | | D04540P | | 41 | | ALL |
| 209R | 20 | | UB | J | 0-0 | 28-41-11 | D04442P | | | | D04540P | | 42 | | ALL |
| 211B | 20 | | UB | M | 30-6 | SPARE | D04442P | | | | D04540P | | 53 | | ALL |
| 211R | 20 | | UB | M | 0-0 | SPARE | D04442P | | | | D04540P | | 54 | | ALL |
| 212B | 20 | | UB | N | 30-6 | SPARE | D04442P | | | | D04540P | | 55 | | ALL |
| 212R | 20 | | UB | N | 0-0 | SPARE | D04442P | | | | D04540P | | 56 | | ALL |
| 213B | 20 | | VG | I | 30-2 | 23-41-11 | D04444P | | | | D04542P | | 7 | | ALL |
| 213R | 20 | | VG | I | 0-0 | 23-41-11 | D04444P | | | | D04542P | | 8 | | ALL |
| 213Z | | | | I | 0-0 | 23-41-11 | D04444P | | | | D04542P | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0400
Page 2
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|---------------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0402 | 286T0402 | | | R WING INBD FS-S2A-FUEL/FIRE DET/ENG INSTR (continued) | | | | | | | | | | | |
| 301B | 20 | UC | A | 30-6 | 28-41-11 | D04540P | | 43 | | | D04442P | 23 | | ALL | |
| 301R | 20 | UC | A | 0-0 | 28-41-11 | D04540P | | 44 | | | D04442P | 24 | | ALL | |
| 301Y | 20 | UC | A | 0-0 | 28-41-11 | D04540P | | 40 | | | D04442P | 20 | | ALL | |
| 302B | 20 | UC | C | 30-3 | 28-41-11 | D04540P | | 23 | | | D04444P | 23 | | ALL | |
| 302R | 20 | UC | C | 0-0 | 28-41-11 | D04540P | | 24 | | | D04444P | 24 | | ALL | |
| 302Y | 20 | UC | C | 0-0 | 28-41-11 | D04540P | | 20 | | | D04444P | 20 | | ALL | |
| 303B | 20 | UC | F | 30-3 | 28-41-11 | D04540P | | 5 | | | D04444P | 5 | | ALL | |
| 303R | 20 | UC | F | 0-0 | 28-41-11 | D04540P | | 6 | | | D04444P | 6 | | ALL | |
| 303Y | 20 | UC | F | 0-0 | 28-41-11 | D04540P | | 2 | | | D04444P | 2 | | ALL | |
| 401B | 20 | UD | L | 30-6 | 28-21-11 | D04442P | | 26 | | | D04540P | 46 | | ALL | |
| 401G | 20 | UD | L | 0-0 | 28-21-11 | D04442P | | 27 | | | D04540P | 47 | | ALL | |
| 401R | 20 | UD | L | 0-0 | 28-21-11 | D04442P | | 28 | | | D04540P | 48 | | ALL | |
| 401Y | 20 | UD | L | 0-0 | 28-21-11 | D04442P | | 29 | | | D04540P | 49 | | ALL | |
| 451R | 18 | XG | | 23-3 | 26-11-12 | D04204J | | 1 | | | D04542P | 1 | | ALL | |
| 452R | 18 | XG | | 23-3 | 26-11-11 | D04204J | | 2 | | | D04542P | 2 | | ALL | |
| 454R | 18 | XG | | 23-3 | 26-11-12 | D04204J | | 18 | | | D04542P | 5 | | ALL | |
| 455R | 18 | XG | | 23-3 | 26-11-11 | D04204J | | 15 | | | D04542P | 4 | | ALL | |
| 456R | 18 | XG | | 23-3 | 26-11-11 | D04204J | | 16 | | | D04542P | 6 | | ALL | |
| 457R | 18 | XG | | 23-3 | 26-11-12 | D04204J | | 14 | | | D04542P | 3 | | ALL | |
| 801 | 20 | UA | | 31-0 | SPARE | D04540P | | 59 | | | D04444P | CAP | Y | 050-099, 150-156, 162-166, 275-276 | |
| W0403 | 286T0403 | | | RIGHT FRONT SPAR SLAT #12 SWITCH | | | | | | | | | | | |
| 001 | 20 | VF | A | 7-11 | 27-89-11 | D07550P | | 2 | | | D03697 | 1 | | 050-099, 151 | |
| 001Z | | | A | 0-0 | 27-89-11 | D07550P | | DED | | | D03697 | DED | | 050-099, 151 | |
| 002 | 20 | VF | B | 7-11 | 27-89-11 | D07550P | | 1 | | | D03697 | 2 | | 050-099, 151 | |
| 002Z | | | B | 0-0 | 27-89-11 | D07550P | | DED | | | D03697 | DED | | 050-099, 151 | |
| W0404 | 286T0404 | | | R WING INBD FS-S2A-FIRE DET/ENG INSTR | | | | | | | | | | | |
| 001 | 20 | UA | | 23-1 | 80-11-21 | D04632P | | 3 | | | D04238J | 4 | | ALL | |
| 002 | 20 | VF | AB | 23-1 | 80-11-21 | D04632P | | 2 | | | D04238J | 5 | | ALL | |
| 002Z | | | AB | 0-0 | 80-11-21 | D04632P | | = CC | L | | D04238J | = CC | M | ALL | |
| 003 | 20 | VF | AC | 23-1 | 80-11-21 | D04632P | | 1 | | | D04238J | 6 | | ALL | |
| 003Z | | | AC | 0-0 | 80-11-21 | D04632P | | = CC | L | | D04238J | = CC | M | ALL | |
| 005 | 20 | UA | | 23-1 | 76-11-11 | D04632P | | 12 | | | D04238J | 8 | | ALL | |
| 006 | 20 | VF | AF | 23-1 | 76-11-11 | D04632P | | 9 | | | D04238J | 9 | | ALL | |
| 006Z | | | AF | 0-0 | 76-11-11 | D04632P | | = CC | L | | D04238J | = CC | M | ALL | |
| 007 | 20 | UA | | 23-1 | 76-11-11 | D04632P | | 5 | | | D04238J | 10 | | ALL | |
| 009 | 20 | VF | AI | 23-1 | 76-11-11 | D04632P | | 10 | | | D04238J | 12 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0400

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0404 | 286T0404 | | | R WING INBD FS-S2A-FIRE DET/ENG INSTR (continued) | | | | | | | | | | | |
| 009Z | | | | AI | 0-0 | 76-11-11 | D04632P | =CC | L | | D04238J | =CC | M | | ALL |
| 451R | 18 | | XG | | 23-1 | 26-11-22 | D05518P | | 6 | | D04238J | | 1 | | ALL |
| 452R | 18 | | XG | | 23-1 | 26-11-21 | D05518P | | 3 | | D04238J | | 15 | | ALL |
| 454R | 18 | | XG | | 23-1 | 26-11-22 | D05518P | | 5 | | D04238J | | 14 | | ALL |
| 455R | 18 | | XG | | 23-1 | 26-11-21 | D05518P | | 2 | | D04238J | | 16 | | ALL |
| 456R | 18 | | XG | | 23-1 | 26-11-21 | D05518P | | 1 | | D04238J | | 2 | | ALL |
| 457R | 18 | | XG | | 23-1 | 26-11-22 | D05518P | | 4 | | D04238J | | 18 | | ALL |
| W0406 | 286T0406 | | | L WING INBD FS-L2A-HYDRAULICS/ENGINE INSTRUMENTS/FLIGHT CONTROLS | | | | | | | | | | | |
| 001 | 20 | | UA | | 23-0 | 36-11-61 | D04212J | | 1 | | D04484P | | 1 | | ALL |
| 002 | 20 | | UA | | 23-0 | 36-11-61 | D04212J | | 2 | | D04484P | | 2 | | ALL |
| 003 | 18 | | UA | | 23-0 | 36-11-61 | D04212J | | 3 | | D04484P | | 3 | DL | ALL |
| 005 | 18 | | UA | | 23-0 | 36-11-61 | D04212J | | 5 | | D04484P | | 5 | DL | ALL |
| 006 | 20 | | UA | | 23-0 | 36-11-61 | D04212J | | 6 | | D04484P | | 6 | | ALL |
| 007 | 20 | | UA | | 23-0 | 36-11-61 | D04212J | | 7 | | D04484P | | 7 | | ALL |
| 008 | 20 | | UA | | 23-0 | 36-11-61 | D04484P | | 40 | | D04212J | | 8 | | ALL |
| 009 | 20 | | UA | | 23-0 | 36-11-61 | D04212J | | 9 | | D04484P | | 41 | | ALL |
| 010 | 20 | | UA | | 23-0 | 36-11-61 | D04212J | | 10 | | D04484P | | 10 | | ALL |
| 011 | 20 | | UA | | 23-0 | 36-11-61 | D04212J | | 11 | | D04484P | | 8 | | ALL |
| 015 | 20 | | UA | | 23-0 | 74-31-11 | D04212J | | 15 | | D04482P | | 5 | | ALL |
| 016 | 20 | | VF | AP | 23-0 | 79-35-11 | D04212J | | 16 | | D04482P | | 6 | | ALL |
| 016Z | | | | AP | 0-0 | 79-35-11 | D04212J | =CC | | M | D04482P | =CC | | M | ALL |
| 017 | 20 | | UA | | 23-0 | 30-21-11 | D04212J | | 24 | | D04482P | | 15 | | ALL |
| 018 | 20 | | UA | | 23-0 | 30-21-11 | D04212J | | 23 | | D04482P | | 1 | | ALL |
| 019 | 20 | | UA | | 23-0 | 30-21-11 | D04212J | | 25 | | D04482P | | 14 | | ALL |
| 01TI | | | | E | 0-0 | 77-31-11 | D04482P | | 29 | | D06292J | | 3 | | 050-099 |
| 01TI | | | | A | 0-0 | 77-31-11 | D04482P | | 29 | | D06292J | | 3 | | 155-199, 277-299 |
| 01TO | | | | E | 0-0 | 77-31-11 | D04482P | =CC | | M | D06292J | =CC | | M | 050-099 |
| 01TO | | | | A | 0-0 | 77-31-11 | D04482P | =CC | | M | D06292J | =CC | | M | 155-199, 277-299 |
| 01TR | 20 | | RQ | E | 24-0 | 77-31-11 | D04482P | | 27 | | D06292J | | 2 | | 050-099 |
| 01TR | 20 | | RQ | A | 24-0 | 77-31-11 | D04482P | | 27 | | D06292J | | 2 | | 155-199, 277-299 |
| 01TW | 20 | | RQ | E | 0-0 | 77-31-11 | D04482P | | 28 | | D06292J | | 1 | | 050-099 |
| 01TW | 20 | | RQ | A | 0-0 | 77-31-11 | D04482P | | 28 | | D06292J | | 1 | | 155-199, 277-299 |
| 023 | 20 | | UA | | 23-0 | 30-21-11 | D04212J | | 4 | | D04482P | | 41 | | ALL |
| 028 | 20 | | VF | BC | 23-0 | 79-33-11 | D04212J | | 22 | | D04482P | | 17 | | ALL |
| 028Z | | | | BC | 0-0 | 79-33-11 | D04212J | =CC | | M | D04482P | =CC | | M | ALL |
| 029 | 20 | | UA | | 10-0 | SPARE | D04214J | | 3 | | D04474P | CAP | | Y | ALL |
| 030 | 20 | | UA | | 10-0 | SPARE | D04214J | | 4 | | D04474P | | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0400
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|----|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0406 | 286T0406 | | | L WING INBD FS-L2A-HYDRAULICS/ENGINE INSTRUMENTS/FLIGHT CONTROLS (continued) | | | | | | | | | | | | | |
| 032 | 20 | | UA | 23-0 | 36-11-61 | D11158 | | 2 | | | | | D04484P | 42 | | | 050-099, 150-155, 163-165, 275-276 |
| 032 | 20 | | UA | 24-0 | 36-11-61 | D11158 | | 2 | | | | | D04484P | 42 | | | 156-162, 166-199, 277-299 |
| 033R | 18 | | XG | 23-0 | 26-18-12 | D04484P | | 11 | DL | | | | D04214J | 21 | | | ALL |
| 034R | 18 | | XG | 23-0 | 26-18-12 | D04484P | | 17 | DL | | | | D04214J | 14 | | | ALL |
| 040 | 20 | | UA | 24-0 | 36-22-11 | D04206J | | 1 | | | | | D04486P | 32 | | | ALL |
| 041 | 20 | | UA | 23-0 | 36-11-51 | D04206J | | 2 | | | | | D04484P | 18 | | | ALL |
| 042 | 20 | | UA | 23-0 | 36-11-51 | D04206J | | 3 | | | | | D04484P | 19 | | | ALL |
| 043 | 18 | | UA | 23-0 | 36-11-51 | D04206J | | 4 | | | | | D04484P | 20 | DL | | ALL |
| 044 | 18 | | UA | 23-0 | SPARE | D04206J | | 5 | | | | | D04484P | 21 | DL | | ALL |
| 045 | 18 | | UA | 23-0 | 36-11-51 | D04206J | | 6 | | | | | D04484P | 22 | DL | | ALL |
| 046 | 20 | | UA | 23-0 | 36-11-51 | D04206J | | 7 | | | | | D04484P | 23 | | | ALL |
| 047 | 20 | | UA | 23-0 | 36-11-51 | D04206J | | 8 | | | | | D04484P | 24 | | | ALL |
| 048 | 20 | | UA | 23-0 | 36-23-11 | D04206J | | 9 | | | | | D04484P | 25 | | | ALL |
| 050 | 20 | | UA | 23-0 | 36-23-11 | D04206J | | 11 | | | | | D04484P | 26 | | | ALL |
| 051 | 20 | | UA | 23-0 | 36-23-11 | D04206J | | 12 | | | | | D04484P | 27 | | | ALL |
| 055 | 20 | | UA | 23-0 | 36-23-11 | D04206J | | 18 | | | | | D04484P | 33 | | | ALL |
| 056 | 20 | | UA | 23-0 | 36-23-11 | D04206J | | 17 | | | | | D04484P | 32 | | | ALL |
| 058 | 20 | | VF | 23-0 | 75-23-11 | D04214J | | 5 | | | | | D04482P | 7 | | | ALL |
| 058Z | | | | 0-0 | 75-23-11 | D04214J | | = CC | M | | | | D04482P | = CC | M | | ALL |
| 059 | 20 | | VF | 23-0 | 75-23-11 | D04214J | | 6 | | | | | D04482P | 12 | | | ALL |
| 059Z | | | | 0-0 | 75-23-11 | D04214J | | = CC | M | | | | D04482P | = CC | M | | ALL |
| 060 | 20 | | UA | 30-0 | 78-34-11 | D04474P | | 3 | | | | | D04482P | 38 | | | ALL |
| 061 | 20 | | UA | 30-0 | 29-32-11 | D04474P | | 9 | | | | | D04484P | 36 | | | ALL |
| 062 | 20 | | UA | 30-0 | 29-32-11 | D04474P | | 5 | | | | | D04484P | 37 | | | ALL |
| 067 | 20 | | VF | 30-0 | 29-33-11 | D04474P | | 12 | | | | | D04484P | 53 | | | ALL |
| 067Z | | | | 0-0 | 29-33-11 | D04474P | | | | FA | | | D04484P | | | FB | ALL |
| 068 | 20 | | UA | 30-0 | 29-33-11 | D04474P | | 14 | | | | | D04484P | 43 | | | ALL |
| 069 | 20 | | UA | 30-0 | 29-33-11 | D04474P | | 15 | | | | | D04484P | 44 | | | ALL |
| 070 | 20 | | UA | 30-0 | 29-33-11 | D04474P | | 10 | | | | | D04484P | 45 | | | ALL |
| 072 | 18 | | UA | 30-0 | 78-36-11 | D04482P | | 40 | DL | | | | D04474P | 6 | | | ALL |
| 073 | 18 | | UA | 30-0 | 78-36-11 | D04482P | | 13 | DL | | | | D04474P | 8 | | | 050-099, 150-156, 162-199, 275-299 |
| 073 | 18 | | UA | 30-0 | SPARE | D04482P | | 13 | DL | | | | D04474P | 8 | | | 157 |
| 075 | 20 | | UA | 30-0 | 29-32-11 | D04474P | | 16 | | | | | D04484P | 46 | | | ALL |
| 081 | 20 | | UA | 23-0 | SPARE | D04206J | | 25 | | | | | D04484P | CAP | Y | | 050-099 |
| 081 | 20 | | UA | 23-0 | SPARE | D04206J | | 25 | | | | | D04484P | 4 | | | 150-199, 275-299 |
| 082 | 20 | | UA | 23-0 | SPARE | D04206J | | 26 | | | | | D04484P | 12 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0400

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|---------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0406 | 286T0406 | | | L WING INBD FS-L2A-HYDRAULICS/ENGINE INSTRUMENTS/FLIGHT CONTROLS (continued) | | | | | | | | | | | |
| 083 | 20 | | UA | | 23-0 | SPARE | D04212J | CAP | Y | | D04484P | 13 | | | ALL |
| 084 | 20 | | UA | | 23-0 | SPARE | D04212J | CAP | Y | | D04484P | 14 | | | ALL |
| 085 | 20 | | UA | | 23-0 | SPARE | D04212J | CAP | Y | | D04484P | 15 | | | ALL |
| 086 | 20 | | VF | DK | 23-0 | 30-21-11 | D04212J | | | 26 | D04482P | 8 | | | ALL |
| 086Z | | | | DK | 0-0 | 30-21-11 | D04212J | = CC | M | | D04482P | = CC | M | | ALL |
| 087R | 18 | | XG | | 23-0 | 26-18-11 | D04484P | | | 55 | DL | D04206J | 24 | | ALL |
| 089 | 20 | | UA | | 30-0 | 29-11-12 | D04474P | | | 17 | | D04484P | 51 | | ALL |
| 093 | 20 | | VF | B | 23-0 | 78-36-11 | D04214J | | | 9 | | D04482P | 9 | | ALL |
| 093Z | | | | B | 0-0 | 78-36-11 | D04214J | = CC | M | | D04482P | = CC | M | | ALL |
| 099 | 18 | | VF | DX | 35-0 | 78-34-11 | D04482P | | | 54 | DL | D04474P | 1 | | 050-099, 150-156, 162-166, 275-276 |
| 099 | 18 | | VF | DX | 32-0 | 78-34-11 | D04482P | | | 54 | DL | D04474P | 1 | | 157, 167-199, 277-299 |
| 099Z | | | | DX | 0-0 | 78-34-11 | D04482P | = CC | M | | D04474P | DED | | | ALL |
| 101 | 20 | | UA | | 32-0 | SPARE | D04486P | | | 23 | | D04434P | 23 | | ALL |
| 110 | 20 | | VF | EJ | 23-0 | 75-23-11 | D04214J | | | 7 | | D04482P | 50 | | ALL |
| 110Z | | | | EJ | 0-0 | 75-23-11 | D04214J | = CC | M | | D04482P | = CC | M | | ALL |
| 111 | 20 | | VF | EK | 23-0 | 75-23-11 | D04214J | | | 8 | | D04482P | 51 | | ALL |
| 111Z | | | | EK | 0-0 | 75-23-11 | D04214J | = CC | M | | D04482P | = CC | M | | ALL |
| 115 | 20 | | UA | | 5-0 | 36-11-61 | D04212J | | | 20 | | D11158 | 1 | | 050-099, 150-155, 162-165, 275-276 |
| 115 | 20 | | UA | | 5-0 | 36-11-61 | D11158 | | | 1 | | D04212J | 20 | | 156-157, 166-199, 277-299 |
| 116 | 18 | | UA | | 25-0 | 36-11-61 | D11158 | | | 3 | DK | GD04550 | S.. | N | 050-099, 150-155, 162-165, 275-276 |
| 116 | 18 | | UA | | 7-0 | 36-11-61 | D11158 | | | 3 | DK | GD04550 | S.. | N | 156-157, 166-199, 277-299 |
| 117 | 20 | | UA | | 25-0 | 36-11-61 | D13942 | | | 3 | | D04484P | 9 | | 050-099, 150-155, 162-165, 275-276 |
| 117 | 20 | | UA | | 24-0 | 36-11-61 | D13942 | | | 3 | | D04484P | 9 | | 156-157, 166-199, 277-299 |
| 118 | 18 | | UA | | 25-0 | 36-11-61 | D13942 | | | 5 | DK | GD04550 | S.. | N | 050-099, 150-155, 162-165, 275-276 |
| 118 | 18 | | UA | | 7-0 | 36-11-61 | D13942 | | | 5 | DK | GD04550 | S.. | N | 156-157, 166-199, 277-299 |
| 124 | 18 | | VF | EX | 35-0 | 78-34-11 | D04482P | | | 55 | DL | D04474P | 7 | | 050-099, 150-156, 162-166, 275-276 |
| 124 | 18 | | VF | EX | 32-0 | 78-34-11 | D04482P | | | 55 | DL | D04474P | 7 | | 157, 167-199, 277-299 |
| 124Z | | | | EX | 0-0 | 78-34-11 | D04482P | = CC | M | | D04474P | DED | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0400
Page 6
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0406 | 286T0406 | | | L WING INBD FS-L2A-HYDRAULICS/ENGINE INSTRUMENTS/FLIGHT CONTROLS (continued) | | | | | | | | | | | |
| 125 | 18 | VF | EY | 28-0 | 78-36-11 | D04486P | | 33 | DL | | D04214J | | 1 | | 050-099, 150-156, 162-166, 275-276 |
| 125 | 18 | VF | EY | 25-0 | 78-36-11 | D04486P | | 33 | DL | | D04214J | | 1 | | 157, 167-199, 277-299 |
| 125Z | | | EY | 0-0 | 78-36-11 | D04486P | =CC | M | | | D04214J | =CC | M | | ALL |
| 126 | 18 | VF | FA | 28-0 | 78-36-11 | D04486P | | 34 | DL | | D04214J | | 18 | | 050-099, 150-156, 162-166, 275-276 |
| 126 | 18 | VF | FA | 25-0 | 78-36-11 | D04486P | | 34 | DL | | D04214J | | 18 | | 157, 167-199, 277-299 |
| 126Z | | | FA | 0-0 | 78-36-11 | D04486P | =CC | M | | | D04214J | =CC | M | | ALL |
| 127 | 18 | UA | | 1-0 | 78-36-11 | D04474P | | 18 | | | SM00005 | | 9 | | ALL |
| 128 | 18 | UA | | 1-0 | 78-36-11 | SM00006 | | | 9 | | D04474P | | 19 | | ALL |
| 130 | 18 | UA | | 29-6 | 78-36-11 | SM00005 | | | 9 | | D04482P | | 39 | DL | ALL |
| 131 | 18 | UA | | 29-10 | 78-36-11 | SM00006 | | | 9 | | D04486P | | 39 | DL | ALL |
| 132 | 18 | UA | | 8-9 | 78-36-11 | SM00005 | | | 9 | | D04206J | | 22 | | ALL |
| 133 | 18 | UA | | 8-9 | 78-36-11 | SM00006 | | | 9 | | D04206J | | 23 | | ALL |
| 203R | 20 | RJ | W | 24-0 | 77-31-11 | D06292J | | 2 | | | D04482P | | 27 | | 150-154, 275-276 |
| 203W | 20 | RJ | W | 0-0 | 77-31-11 | D06292J | | 1 | | | D04482P | | 28 | | 150-154, 275-276 |
| 203Z | | | W | 0-0 | 77-31-11 | D06292J | | 3 | | | D04482P | | 29 | | 150-154, 275-276 |
| 204B | 20 | UB | ID | 23-0 | 78-36-11 | D04482P | | 30 | | | D04214J | | 30 | | ALL |
| 204R | 20 | UB | ID | 0-0 | 78-36-11 | D04482P | | 31 | | | D04214J | | 29 | | ALL |
| 205B | 20 | UB | IE | 23-0 | 78-36-11 | D04482P | | 32 | | | D04214J | | 23 | | ALL |
| 205R | 20 | UB | IE | 0-0 | 78-36-11 | D04482P | | 33 | | | D04214J | | 24 | | ALL |
| 206B | 20 | UB | IF | 23-0 | 78-36-11 | D04482P | | 34 | | | D04214J | | 25 | | ALL |
| 206R | 20 | UB | IF | 0-0 | 78-36-11 | D04482P | | 35 | | | D04214J | | 26 | | ALL |
| 207B | 20 | UB | IG | 23-0 | 78-36-11 | D04482P | | 36 | | | D04214J | | 27 | | ALL |
| 207R | 20 | UB | IG | 0-0 | 78-36-11 | D04482P | | 37 | | | D04214J | | 28 | | ALL |
| 208B | 20 | UB | H | 32-0 | 27-88-12 | D04434P | | 15 | | | D04486P | | 15 | | ALL |
| 208R | 20 | UB | H | 0-0 | 27-88-12 | D04434P | | 16 | | | D04486P | | 16 | | ALL |
| 209B | 20 | UB | J | 32-0 | 27-88-12 | D04434P | | 17 | | | D04486P | | 17 | | ALL |
| 209R | 20 | UB | J | 0-0 | 27-88-12 | D04434P | | 18 | | | D04486P | | 18 | | ALL |
| 211B | 20 | UB | L | 32-0 | 27-88-12 | D04434P | | 21 | | | D04486P | | 21 | | ALL |
| 211R | 20 | UB | L | 0-0 | 27-88-12 | D04434P | | 22 | | | D04486P | | 22 | | ALL |
| 212B | 20 | UB | M | 32-0 | 27-88-12 | D04434P | | 3 | | | D04486P | | 3 | | ALL |
| 212R | 20 | UB | M | 0-0 | 27-88-12 | D04434P | | 4 | | | D04486P | | 4 | | ALL |
| 216B | 20 | UB | P | 32-0 | 27-88-12 | D04434P | | 9 | | | D04486P | | 9 | | ALL |
| 216R | 20 | UB | P | 0-0 | 27-88-12 | D04434P | | 10 | | | D04486P | | 10 | | ALL |
| 220B | 20 | UB | A | 32-0 | 27-88-12 | D04434P | | 1 | | | D04486P | | 1 | | 050-099, 150-154, 275-276 |
| 220B | 20 | UB | IT | 32-0 | 27-88-12 | D04434P | | 1 | | | D04486P | | 1 | | 155-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0400

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|---------|------|------|--------|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0406 | 286T0406 | | | L WING INBD FS-L2A-HYDRAULICS/ENGINE INSTRUMENTS/FLIGHT CONTROLS (continued) | | | | | | | | | | | |
| 220R | 20 | UB | A | 0-0 | 27-88-12 | D04434P | | 2 | | D04486P | | 2 | | | 050-099, 150-154, 275-276 |
| 220R | 20 | UB | IT | 0-0 | 27-88-12 | D04434P | | 2 | | D04486P | | 2 | | | 155-199, 277-299 |
| 222B | 20 | UB | C | 32-0 | 27-88-12 | D04434P | | 5 | | D04486P | | 5 | | | ALL |
| 222R | 20 | UB | C | 0-0 | 27-88-12 | D04434P | | 6 | | D04486P | | 6 | | | ALL |
| 223B | 20 | UB | D | 32-0 | 27-88-12 | D04434P | | 7 | | D04486P | | 7 | | | ALL |
| 223R | 20 | UB | D | 0-0 | 27-88-12 | D04434P | | 8 | | D04486P | | 8 | | | ALL |
| 225B | 20 | UB | F | 32-0 | 27-88-12 | D04434P | | 11 | | D04486P | | 11 | | | ALL |
| 225R | 20 | UB | F | 0-0 | 27-88-12 | D04434P | | 12 | | D04486P | | 12 | | | ALL |
| 226B | 20 | UB | G | 32-0 | 27-88-12 | D04434P | | 13 | | D04486P | | 13 | | | ALL |
| 226R | 20 | UB | G | 0-0 | 27-88-12 | D04434P | | 14 | | D04486P | | 14 | | | ALL |
| 227B | 20 | UB | AB | 15-0 | 27-88-12 | SP00166 | | | 9 | D04486P | | 19 | | | ALL |
| 227R | 20 | UB | AB | 0-0 | 27-88-12 | SP00168 | | | 9 | D04486P | | 20 | | | ALL |
| 228B | 20 | UB | AC | 24-0 | 27-88-12 | SP00170 | | | 9 | D04486P | | 25 | | | ALL |
| 228R | 20 | UB | AC | 0-0 | 27-88-12 | SP00172 | | | 9 | D04486P | | 26 | | | ALL |
| 230B | 20 | UB | T | 23-0 | SPARE | D04212J | | | CAP | Y | D04482P | | 10 | | 150-199, 275-299 |
| 230R | 20 | UB | T | 0-0 | SPARE | D04212J | | | CAP | Y | D04482P | | 11 | | 150-199, 275-299 |
| 231B | 20 | UB | JF | 23-0 | 36-22-21 | D04484P | | | 39 | D04206J | | 20 | | | 050-099 |
| 231B | 20 | UB | AF | 23-0 | 36-22-21 | D04484P | | | 39 | D04206J | | 20 | | | 150-199, 275-299 |
| 231R | 20 | UB | JF | 0-0 | 36-22-21 | D04484P | | | 38 | D04206J | | 19 | | | 050-099 |
| 231R | 20 | UB | AF | 0-0 | 36-22-21 | D04484P | | | 38 | D04206J | | 19 | | | 150-199, 275-299 |
| 245B | 20 | VG | JT | 24-0 | 36-11-61 | D13942 | | | 2 | D04484P | | 49 | | | ALL |
| 245R | 20 | VG | JT | 0-0 | 36-11-61 | D13942 | | | 1 | D04484P | | 50 | | | ALL |
| 245Z | | | JT | 0-0 | 36-11-61 | D13942 | | | =CC | L | D04484P | | =CC | M | ALL |
| 248B | 18 | VG | JX | 28-0 | 78-36-11 | D04486P | | | 28 | DL | D04214J | | 17 | | 050-099, 150-156, 162-166, 275-276 |
| 248B | 18 | VG | JX | 25-0 | 78-36-11 | D04486P | | | 28 | DL | D04214J | | 17 | | 157, 167-199, 277-299 |
| 248R | 18 | VG | JX | 0-0 | 78-36-11 | D04486P | | | 36 | DL | D04214J | | 16 | | ALL |
| 248Z | | | JX | 0-0 | 78-36-11 | D04486P | | | =CC | M | D04214J | | =CC | M | ALL |
| 249B | 18 | VG | JW | 28-0 | 78-36-11 | D04486P | | | 38 | DL | D04214J | | 20 | | 050-099, 150-156, 162-166, 275-276 |
| 249B | 18 | VG | JW | 25-0 | 78-36-11 | D04486P | | | 38 | DL | D04214J | | 20 | | 157, 167-199, 277-299 |
| 249R | 18 | VG | JW | 0-0 | 78-36-11 | D04486P | | | 31 | DL | D04214J | | 19 | | ALL |
| 249Z | | | JW | 0-0 | 78-36-11 | D04486P | | | =CC | M | D04214J | | =CC | M | ALL |
| 250B | 18 | UB | AR | 36-0 | 27-89-11 | D04434P | | | 20 | | D04486P | | 43 | DL | ALL |
| 250R | 18 | UB | AR | 0-0 | 27-89-11 | D04434P | | | 19 | | D04486P | | 42 | DL | ALL |
| 251B | 18 | VG | JV | 27-0 | 78-36-11 | D04486P | | | 35 | DL | D04214J | | 10 | | 050-099, 150-156, 162-166, 275-276 |
| 251B | 18 | VG | JV | 25-0 | 78-36-11 | D04486P | | | 35 | DL | D04214J | | 10 | | 157, 167-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0400
Page 8
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|--------|------|------|--------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0406 | 286T0406 | | | L WING INBD FS-L2A-HYDRAULICS/ENGINE INSTRUMENTS/FLIGHT CONTROLS (continued) | | | | | | | | | | | | |
| 251R | 18 | VG | JV | 0-0 | 78-36-11 | D04486P | 37 | DL | | D04214J | 11 | | | | ALL | |
| 251Z | | | JV | 0-0 | 78-36-11 | D04486P | =CC | M | | D04214J | =CC | M | | | ALL | |
| 252B | 18 | VG | YY | 27-0 | 78-36-11 | D04486P | 40 | DL | | D04214J | 12 | | | | 050-099, 150-156, 162-166, 275-276 | |
| 252B | 18 | VG | YY | 25-0 | 78-36-11 | D04486P | 40 | DL | | D04214J | 12 | | | | 157, 167-199, 277-299 | |
| 252R | 18 | VG | YY | 0-0 | 78-36-11 | D04486P | 41 | DL | | D04214J | 13 | | | | ALL | |
| 252Z | | | YY | 0-0 | 78-36-11 | D04486P | =CC | M | | D04214J | =CC | M | | | ALL | |
| 301B | 20 | VH | AD | 23-0 | 36-23-11 | D04206J | 13 | | | D04484P | 28 | | | | ALL | |
| 301R | 20 | VH | AD | 0-0 | 36-23-11 | D04206J | 14 | | | D04484P | 29 | | | | ALL | |
| 301Y | 20 | VH | AD | 0-0 | 36-23-11 | D04206J | 15 | | | D04484P | 30 | | | | ALL | |
| 301Z | | | AD | 0-0 | 36-23-11 | D04206J | 16 | | | D04484P | 31 | | | | ALL | |
| 302B | 20 | VH | AG | 23-0 | 73-31-11 | D04482P | 25 | | | D04212J | 18 | | | | ALL | |
| 302R | 20 | VH | AG | 0-0 | 73-31-11 | D04482P | 24 | | | D04212J | 17 | | | | ALL | |
| 302Y | 20 | VH | AG | 0-0 | 73-31-11 | D04482P | 26 | | | D04212J | 19 | | | | ALL | |
| 302Z | | | AG | 0-0 | 73-31-11 | D04482P | 23 | | | D04212J | =CC | M | | | ALL | |
| 303B | 20 | VH | MC | 23-0 | 79-31-11 | D04212J | 12 | | | D04482P | 2 | | | | ALL | |
| 303R | 20 | VH | MC | 0-0 | 79-31-11 | D04212J | 14 | | | D04482P | 4 | | | | ALL | |
| 303Y | 20 | VH | MC | 0-0 | 79-31-11 | D04212J | 13 | | | D04482P | 3 | | | | ALL | |
| 303Z | | | MC | 0-0 | 79-31-11 | D04212J | =CC | M | | D04482P | =CC | M | | | ALL | |
| 304B | 20 | VH | MD | 24-0 | 73-33-11 | D04482P | 49 | | | D04212J | 29 | | | | 050-099 | |
| 304B | 20 | VH | MD | 23-0 | 73-33-11 | D04482P | 49 | | | D04212J | 29 | | | | 150-199, 275-299 | |
| 304R | 20 | VH | MD | 0-0 | 73-33-11 | D04482P | 47 | | | D04212J | 27 | | | | ALL | |
| 304Y | 20 | VH | MD | 0-0 | 73-33-11 | D04482P | 48 | | | D04212J | 28 | | | | ALL | |
| 304Z | | | MD | 0-0 | 73-33-11 | D04482P | =CC | M | | D04212J | =CC | M | | | ALL | |
| 801 | 20 | UA | | 32-0 | SPARE | D04486P | 24 | | | D04434P | 24 | | | | ALL | |
| A-A | | | | 0-0 | SPARE | SP00166 | | 9 | | | S00281 | BLU | | | ALL | |
| A-B | | | | 0-0 | 27-88-12 | SP00168 | | 9 | | | S00281 | RED | | | ALL | |
| A-C | | | | 0-0 | 27-88-12 | SP00170 | | 9 | | | S00287 | BLU | | | ALL | |
| A-D | | | | 0-0 | 27-88-12 | SP00172 | | 9 | | | S00287 | RED | | | ALL | |
| FRA | | | | 0-0 | 29-33-11 | D04474P | | | FA | D04474P | 4 | | | | ALL | |
| FRB | | | | 0-0 | 29-33-11 | D04474P | | | FA | D04474P | 11 | | | | ALL | |
| FRC | | | | 0-0 | 29-33-11 | D04474P | | | FA | D04474P | 13 | | | | ALL | |
| FRD | | | | 0-0 | 29-33-11 | D04484P | | | FB | D04484P | 34 | | | | ALL | |
| FRE | | | | 0-0 | 29-33-11 | D04484P | | | FB | D04484P | 35 | | | | ALL | |
| FRF | | | | 0-0 | 29-33-11 | D04484P | | | FB | D04484P | 54 | | | | ALL | |
| W0407 | 286T0407 | | | ADC SWITCHING S,SHELF TO P36 & P37 | | | | | | | | | | | | |
| 001 | 22 | PA | | 20-0 | SPARE | D04705J | | 1 | | D04745P | 1 | | | | ALL | |
| 002 | 22 | PA | | 34-0 | SPARE | D04705J | | 2 | | D04743P | 2 | | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0400

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|---|-------|------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0407 | 286T0407 | ADC SWITCHING S,SHELF TO P36 & P37 (continued) | | | | | | | | | | | | | |
| 003 | 22 | PA | | 34-0 | SPARE | D04705J | | 3 | | D04743P | | 3 | | ALL | |
| 004 | 24 | PK | | 34-0 | 33-16-14 | D04705J | | 4 | | D04743P | | 4 | | ALL | |
| 009 | 22 | PA | | 34-0 | 34-12-11 | D04743P | | 9 | | D04705J | | 29 | | ALL | |
| 010 | 22 | PA | | 34-0 | 34-12-11 | D04743P | | 10 | | D04705J | | 30 | | ALL | |
| 011 | 22 | PA | | 34-0 | 34-12-11 | D04743P | | 11 | | D04705J | | 31 | | ALL | |
| 015 | 22 | PA | | 34-0 | 32-45-11 | D04705J | | 14 | | D04743P | | 19 | | 050-099, 150-199 | |
| 016 | 22 | PA | | 20-0 | 32-45-11 | D04705J | | 15 | | D04745P | | 2 | | 050-099, 150-199 | |
| 017 | 22 | PA | | 20-0 | 32-45-11 | D04743P | | 20 | | D04745P | | 3 | | 050-099, 150-199 | |
| 207B | 20 | PR | IG | 19-0 | 32-45-12 | D04745P | | 11 | | D04705J | | 22 | | 050-099 | |
| 207B | 20 | PR | IG | 20-0 | 32-45-12 | D04745P | | 11 | | D04705J | | 22 | | 150-199 | |
| 207R | 20 | PR | IG | 0-0 | 32-45-12 | D04745P | | 10 | | D04705J | | 21 | | 050-099, 150-199 | |
| 207Z | | | IG | 0-0 | 32-45-12 | D04745P | | 12 | | D04705J | | 17 | | 050-099, 150-199 | |
| 208B | 24 | PW | IH | 20-0 | SPARE | D04705J | | 19 | | D04745P | | 19 | | ALL | |
| 208R | 24 | PW | IH | 0-0 | SPARE | D04705J | | 18 | | D04745P | | 18 | | ALL | |
| 208Z | | | IH | 0-0 | SPARE | D04705J | | 20 | | D04745P | | 20 | | ALL | |
| 209B | 24 | PW | II | 20-0 | 32-42-11 | D04745P | | 5 | | D04705J | | 25 | | ALL | |
| 209R | 24 | PW | II | 0-0 | 32-42-11 | D04745P | | 4 | | D04705J | | 24 | | ALL | |
| 209Z | | | II | 0-0 | 32-42-11 | D04745P | | 6 | | D04705J | | 26 | | ALL | |
| 210B | 20 | PR | IJ | 19-0 | 32-45-12 | D04745P | | 14 | | D04705J | | 28 | | 050-099 | |
| 210B | 20 | PR | IJ | 20-0 | 32-45-12 | D04745P | | 14 | | D04705J | | 28 | | 150-199 | |
| 210R | 20 | PR | IJ | 0-0 | 32-45-12 | D04745P | | 13 | | D04705J | | 27 | | 050-099, 150-199 | |
| 210Z | | | IJ | 0-0 | 32-45-12 | D04745P | | 15 | | D04705J | | 23 | | 050-099, 150-199 | |
| W0408 | 286T0408 | R WING INBD FS-R2A-HYDRAULICS/ENGINE INSTRUMENTS/FLIGHT CONTROLS | | | | | | | | | | | | | |
| 001 | 20 | UA | | 24-0 | 36-11-62 | D05528P | | 1 | | D04252J | | 1 | | ALL | |
| 002 | 20 | UA | | 24-0 | 36-11-62 | D05528P | | 2 | | D04252J | | 2 | | ALL | |
| 003 | 18 | UA | | 24-0 | 36-11-62 | D05528P | | 3 | DL | D04252J | | 3 | | ALL | |
| 004 | 18 | UA | | 24-0 | SPARE | D05528P | | 4 | DL | D04248J | | 5 | | ALL | |
| 005 | 18 | UA | | 24-0 | 36-11-62 | D05528P | | 5 | DL | D04252J | | 5 | | ALL | |
| 006 | 20 | UA | | 24-0 | 36-11-62 | D05528P | | 6 | | D04252J | | 6 | | ALL | |
| 007 | 20 | UA | | 24-0 | 36-11-62 | D05528P | | 7 | | D04252J | | 7 | | ALL | |
| 008 | 20 | UA | | 24-0 | 36-11-62 | D05528P | | 40 | | D04252J | | 8 | | ALL | |
| 009 | 20 | UA | | 24-0 | 36-11-62 | D05528P | | 41 | | D04252J | | 9 | | ALL | |
| 010 | 20 | UA | | 24-0 | 36-11-62 | D05528P | | 10 | | D04252J | | 10 | | ALL | |
| 011 | 20 | UA | | 24-0 | 36-11-62 | D05528P | | 8 | | D04252J | | 11 | | ALL | |
| 015 | 20 | UA | | 24-0 | 74-31-21 | D04252J | | 15 | | D04616P | | 4 | | ALL | |
| 016 | 20 | VF | AP | 24-0 | 79-35-11 | D04616P | | 5 | | D04252J | | 16 | | ALL | |
| 016Z | | | AP | 0-0 | 79-35-11 | D04616P | | = CC | M | D04252J | | = CC | M | ALL | |
| 017 | 20 | UA | | 24-0 | 30-21-11 | D04616P | | 11 | | D04252J | | 24 | | ALL | |

WIRE LIST

D280T132

91-21-11
 Section W0400
 Page 10
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-----|-------------|---|----|---|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | | |
| W0408 | 286T0408 | | | R WING INBD FS-R2A-HYDRAULICS/ENGINE INSTRUMENTS/FLIGHT CONTROLS (continued) | | | | | | | | | | | | | | | |
| 018 | 20 | | UA | | 24-0 | 30-21-11 | D04616P | | 12 | | | | | D04252J | | 23 | | | ALL |
| 019 | 20 | | UA | | 24-0 | 30-21-11 | D04616P | | 29 | | | | | D04252J | | 25 | | | ALL |
| 01TI | | | | A | 0-0 | 77-31-11 | D04616P | | 28 | | | | | D06296J | | 3 | | | 050-099, 155-199, 277-299 |
| 01TO | | | | A | 0-0 | 77-31-11 | D04616P | =CC | | M | | | | D06296J | =CC | | M | | 050-099, 155-199, 277-299 |
| 01TR | 20 | | RQ | A | 24-0 | 77-31-11 | D04616P | | 26 | | | | | D06296J | | 2 | | | 050-099, 155-199, 277-299 |
| 01TW | 20 | | RQ | A | 0-0 | 77-31-11 | D04616P | | 27 | | | | | D06296J | | 1 | | | 050-099, 155-199, 277-299 |
| 023 | 20 | | UA | | 30-0 | SPARE | D04170P | | 8 | | | | | D04616P | | 46 | | | ALL |
| 024 | 20 | | UA | | 30-0 | 78-36-21 | D04170P | | 6 | | | | | D04616P | | 42 | | | ALL |
| 025 | 20 | | UA | | 24-0 | SPARE | D04616P | | 43 | | | | | D04252J | CAP | | Y | | ALL |
| 028 | 20 | | VF | BC | 24-0 | 79-33-11 | D04616P | | 10 | | | | | D04252J | | 22 | | | ALL |
| 028Z | | | | BC | 0-0 | 79-33-11 | D04616P | =CC | | M | | | | D04252J | =CC | | M | | ALL |
| 029 | 20 | | UA | | 10-0 | SPARE | D04170P | | | CAP | Y | | | D04254J | | 3 | | | ALL |
| 030 | 20 | | UA | | 10-0 | SPARE | D04170P | | 2 | | | | | D04254J | | 4 | | | ALL |
| 031 | 20 | | VF | BF | 24-0 | 75-23-11 | D04254J | | 5 | | | | | D04616P | | 14 | | | ALL |
| 031Z | | | | BF | 0-0 | 75-23-11 | D04254J | =CC | | M | | | | D04616P | =CC | | M | | ALL |
| 032 | 20 | | VF | BG | 24-0 | 75-23-11 | D04254J | | 6 | | | | | D04616P | | 15 | | | ALL |
| 032Z | | | | BG | 0-0 | 75-23-11 | D04254J | =CC | | M | | | | D04616P | =CC | | M | | ALL |
| 042 | 20 | | UA | | 24-0 | 36-11-62 | D05528P | | 13 | | | | | D13022 | | 2 | | | 050-099, 150-155, 163-165, 275-276 156-162, 166-199, 277-299 |
| 042 | 20 | | UA | | 25-0 | 36-11-62 | D05528P | | 13 | | | | | D13022 | | 2 | | | ALL |
| 043 | 20 | | UA | | 30-0 | 78-34-21 | D04616P | | 41 | | | | | D04170P | | 3 | | | ALL |
| 045 | 20 | | UA | | 30-0 | 29-32-11 | D05528P | | 14 | | | | | D04170P | | 9 | | | ALL |
| 046R | 18 | | XG | | 24-0 | 26-18-22 | D05528P | | 51 | DL | | | | D04254J | | 21 | | | ALL |
| 047R | 18 | | XG | | 24-0 | 26-18-22 | D05528P | | 52 | DL | | | | D04254J | | 14 | | | ALL |
| 048 | 20 | | UA | | 30-0 | 29-32-11 | D05528P | | 15 | | | | | D04170P | | 5 | | | ALL |
| 049 | 20 | | UA | | 30-0 | 29-33-11 | D05528P | | 17 | | | | | D04170P | | 10 | | | ALL |
| 051 | 20 | | UA | | 30-0 | 29-33-11 | D05528P | | 19 | | | | | D04170P | | 14 | | | ALL |
| 052 | 20 | | UA | | 30-0 | 29-33-11 | D05528P | | 20 | | | | | D04170P | | 15 | | | ALL |
| 053 | 20 | | VF | J | 30-0 | 29-33-11 | D05528P | | 47 | | | | | D04170P | | 12 | | | ALL |
| 053Z | | | | J | 0-0 | 29-33-11 | D05528P | | | | FB | | | D04170P | | | | FA | ALL |
| 058 | 20 | | UA | | 30-0 | 29-32-11 | D05528P | | 22 | | | | | D04170P | | 16 | | | ALL |
| 059 | 20 | | UA | | 24-0 | 36-22-11 | D05528P | | 23 | | | | | D04248J | | 1 | | | ALL |
| 060 | 20 | | UA | | 24-0 | 36-11-52 | D05528P | | 24 | | | | | D04248J | | 2 | | | ALL |
| 061 | 20 | | UA | | 24-0 | 36-11-52 | D05528P | | 25 | | | | | D04248J | | 3 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0400

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0408 | 286T0408 | | | R WING INBD FS-R2A-HYDRAULICS/ENGINE INSTRUMENTS/FLIGHT CONTROLS (continued) | | | | | | | | | | | | | |
| 062 | 18 | | UA | | 24-0 | 36-11-52 | D05528P | 26 | DL | | | | D04248J | 4 | | | ALL |
| 064 | 18 | | UA | | 24-0 | 36-11-52 | D05528P | 27 | DL | | | | D04248J | 6 | | | ALL |
| 065 | 20 | | UA | | 24-0 | 36-11-52 | D05528P | 49 | | | | | D04248J | 7 | | | ALL |
| 066 | 20 | | UA | | 24-0 | 36-11-52 | D05528P | 50 | | | | | D04248J | 8 | | | ALL |
| 067 | 20 | | UA | | 24-0 | 36-23-21 | D05528P | 30 | | | | | D04248J | 9 | | | ALL |
| 069 | 20 | | UA | | 24-0 | 36-23-21 | D05528P | 31 | | | | | D04248J | 11 | | | ALL |
| 070 | 20 | | UA | | 24-0 | 36-23-21 | D05528P | 32 | | | | | D04248J | 12 | | | ALL |
| 074 | 20 | | UA | | 24-0 | 36-23-21 | D05528P | 44 | | | | | D04248J | 18 | | | ALL |
| 075 | 20 | | UA | | 24-0 | 36-23-21 | D05528P | 37 | | | | | D04248J | 17 | | | ALL |
| 080 | 20 | | UA | | 24-0 | 30-21-11 | D04616P | 45 | | | | | D04252J | 4 | | | ALL |
| 081 | 20 | | UA | | 30-0 | 29-11-22 | D05528P | 9 | | | | | D04170P | 17 | | | ALL |
| 084R | 18 | | XG | | 24-0 | 26-18-21 | D05528P | 18 | DL | | | | D04248J | 24 | | | ALL |
| 086 | 20 | | VF | DK | 24-0 | 30-21-11 | D04616P | 8 | | | | | D04252J | 26 | | | ALL |
| 086Z | | | | DK | 0-0 | 30-21-11 | D04616P | = CC | M | | | | D04252J | = CC | M | | ALL |
| 093 | 20 | | VF | B | 24-0 | 78-36-21 | D04254J | 9 | | | | | D04616P | 9 | | | ALL |
| 093Z | | | | B | 0-0 | 78-36-21 | D04254J | = CC | M | | | | D04616P | = CC | M | | ALL |
| 099 | 18 | | VF | DX | 30-0 | 78-34-21 | D04616P | 16 | DL | | | | D04170P | 7 | | | 050-099, 150-156, 162-166, 275-276 |
| 099 | 18 | | VF | DX | 32-0 | 78-34-21 | D04616P | 6 | DL | | | | D04170P | 7 | | | 157 |
| 099 | 18 | | VF | DX | 32-0 | 78-34-21 | D04616P | 16 | DL | | | | D04170P | 7 | | | 167-199, 277-299 |
| 099Z | | | | DX | 0-0 | 78-34-21 | D04616P | = CC | M | | | | D04170P | DED | | | ALL |
| 110 | 20 | | VF | EJ | 24-0 | 75-23-11 | D04254J | 7 | | | | | D04616P | 39 | | | ALL |
| 110Z | | | | EJ | 0-0 | 75-23-11 | D04254J | = CC | M | | | | D04616P | = CC | M | | ALL |
| 111 | 20 | | VF | EK | 24-0 | 75-23-11 | D04254J | 8 | | | | | D04616P | 40 | | | ALL |
| 111Z | | | | EK | 0-0 | 75-23-11 | D04254J | = CC | M | | | | D04616P | = CC | M | | ALL |
| 116 | 20 | | UA | | 25-0 | 36-11-62 | D04252J | 20 | | | | | D13022 | 1 | | | 050-099, 150-155, 163-165, 275-276 |
| 116 | 20 | | UA | | 4-0 | 36-11-62 | D04252J | 20 | | | | | D13022 | 1 | | | 156-162, 166-199, 277-299 |
| 117 | 18 | | UA | | 25-0 | 36-11-62 | GD04552 | S.. | N | | | | D13022 | 3 | DK | | 050-099, 150-155, 163-165, 275-276 |
| 117 | 18 | | UA | | 8-0 | 36-11-62 | GD04552 | S.. | N | | | | D13022 | 3 | DK | | 156-162, 166-199, 277-299 |
| 118 | 20 | | UA | | 25-0 | 36-11-62 | D05528P | 55 | | | | | D13944 | 3 | | | ALL |
| 119 | 18 | | UA | | 25-0 | 36-11-62 | GD04552 | S.. | N | | | | D13944 | 5 | DK | | 050-099, 150-155, 163-165, 275-276 |
| 119 | 18 | | UA | | 8-0 | 36-11-62 | GD04552 | S.. | N | | | | D13944 | 5 | DK | | 156-162, 166-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0400
Page 12
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | | |
|------------------------|-----------------|----|----|------|---|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W0408 | 286T0408 | | | | R WING INBD FS-R2A-HYDRAULICS/ENGINE INSTRUMENTS/FLIGHT CONTROLS (continued) | | | | | | | | | | | | | |
| 124 | 18 | VF | EX | 30-0 | 78-34-21 | D04616P | | 7 | DL | | | | D04170P | | 1 | | | 050-099, 150-156, 162-166, 275-276 |
| 124 | 18 | VF | EX | 32-0 | 78-34-21 | D04616P | | 7 | DL | | | | D04170P | | 1 | | | 157, 167-199, 277-299 |
| 124Z | | | EX | 0-0 | 78-34-21 | D04616P | | =CC | M | | | | D04170P | | DED | | | ALL |
| 125 | 18 | VF | EY | 25-0 | 78-36-21 | D07040P | | 1 | | | | | D04254J | | 1 | | | 050-099, 150-156, 162-166, 275-276 |
| 125 | 18 | VF | EY | 26-0 | 78-36-21 | D07040P | | 1 | | | | | D04254J | | 1 | | | 157, 167-199, 277-299 |
| 125Z | | | EY | 0-0 | 78-36-21 | D07040P | | =CC | M | | | | D04254J | | =CC | M | | ALL |
| 126 | 18 | VF | FA | 25-0 | 78-36-21 | D07040P | | 2 | | | | | D04254J | | 18 | | | 050-099, 150-156, 162-166, 275-276 |
| 126 | 18 | VF | FA | 26-0 | 78-36-21 | D07040P | | 2 | | | | | D04254J | | 18 | | | 157, 167-199, 277-299 |
| 126Z | | | FA | 0-0 | 78-36-21 | D07040P | | =CC | M | | | | D04254J | | =CC | M | | ALL |
| 127 | 18 | 5A | | 10-0 | 78-36-21 | SM00005 | | | 9 | | | | D04170P | | 18 | | | 050-099, 150-156, 162-166, 275-276 |
| 127 | 18 | UA | | 8-0 | 78-36-21 | SM00005 | | | 9 | | | | D04170P | | 18 | | | 157, 167-199, 277-299 |
| 128 | 18 | 5A | | 10-0 | 78-36-21 | SM00006 | | | 9 | | | | D04170P | | 19 | | | 050-099, 150-156, 162-166, 275-276 |
| 128 | 18 | UA | | 8-0 | 78-36-21 | SM00006 | | | 9 | | | | D04170P | | 19 | | | 157, 167-199, 277-299 |
| 130 | 18 | 5A | | 22-0 | 78-36-21 | D04616P | | 13 | DL | | | | SM00005 | | | 9 | | 050-099, 150-156, 162-166, 275-276 |
| 130 | 18 | UA | | 21-0 | 78-36-21 | D04616P | | 13 | DL | | | | SM00005 | | | 9 | | 157, 167-199, 277-299 |
| 131 | 18 | 5A | | 22-0 | 78-36-21 | D07040P | | 3 | | | | | SM00006 | | | 9 | | 050-099, 150-156, 162-166, 275-276 |
| 131 | 18 | UA | | 21-0 | 78-36-21 | D07040P | | 3 | | | | | SM00006 | | | 9 | | 157, 167-199, 277-299 |
| 132 | 18 | 5A | | 4-0 | 78-36-21 | D04248J | | 22 | | | | | SM00005 | | | 9 | | 050-099, 150-156, 162-166, 275-276 |
| 132 | 18 | UA | | 3-0 | 78-36-21 | D04248J | | 22 | | | | | SM00005 | | | 9 | | 157, 167-199, 277-299 |
| 133 | 18 | 5A | | 4-0 | 78-36-21 | D04248J | | 23 | | | | | SM00006 | | | 9 | | 050-099, 150-156, 162-166, 275-276 |
| 133 | 18 | UA | | 3-0 | 78-36-21 | D04248J | | 23 | | | | | SM00006 | | | 9 | | 157, 167-199, 277-299 |
| 201B | 20 | UB | D | 24-0 | SPARE | D05528P | | 42 | | | | | D04252J | | CAP | Y | | 050-099, 150-156, 162-166, 275-278 |
| 201B | 20 | UB | D | 24-0 | SPARE | D05528P | | 42 | Y | | | | D04252J | | CAP | Y | | 157, 167-199, 280-299 |
| 201R | 20 | UB | D | 0-0 | SPARE | D05528P | | 43 | | | | | D04252J | | CAP | Y | | ALL |
| 204R | 20 | RJ | C | 24-0 | 77-31-11 | D04616P | | 26 | | | | | D06296J | | 2 | | | 150-154, 275-276 |
| 204W | 20 | RJ | C | 0-0 | 77-31-11 | D04616P | | 27 | | | | | D06296J | | 1 | | | 150-154, 275-276 |
| 204Z | | | C | 0-0 | 77-31-11 | D04616P | | 28 | | | | | D06296J | | 3 | | | 150-154, 275-276 |
| 205B | 20 | UB | IE | 24-0 | 78-36-21 | D04616P | | 30 | | | | | D04254J | | 30 | | | ALL |
| 205R | 20 | UB | IE | 0-0 | 78-36-21 | D04616P | | 31 | | | | | D04254J | | 29 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0400

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0408 | 286T0408 | | | R WING INBD FS-R2A-HYDRAULICS/ENGINE INSTRUMENTS/FLIGHT CONTROLS (continued) | | | | | | | | | | | |
| 206B | 20 | UB | IF | | 24-0 | 78-36-21 | D04616P | | | | D04254J | 23 | | | ALL |
| 206R | 20 | UB | IF | | 0-0 | 78-36-21 | D04616P | | | | D04254J | 24 | | | ALL |
| 207B | 20 | UB | IG | | 24-0 | 78-36-21 | D04616P | | | | D04254J | 25 | | | ALL |
| 207R | 20 | UB | IG | | 0-0 | 78-36-21 | D04616P | | | | D04254J | 26 | | | ALL |
| 208B | 20 | UB | IH | | 24-0 | 78-36-21 | D04616P | | | | D04254J | 27 | | | ALL |
| 208R | 20 | UB | IH | | 0-0 | 78-36-21 | D04616P | | | | D04254J | 28 | | | ALL |
| 209B | 20 | UB | L | | 24-0 | 36-22-21 | D05528P | | | | D04248J | 20 | | | ALL |
| 209R | 20 | UB | L | | 0-0 | 36-22-21 | D05528P | | | | D04248J | 19 | | | ALL |
| 223B | 20 | VG | IW | | 25-0 | 36-11-62 | D05528P | | | | D13944 | 2 | | | ALL |
| 223R | 20 | VG | IW | | 0-0 | 36-11-62 | D05528P | | | | D13944 | 1 | | | ALL |
| 223Z | | | IW | | 0-0 | 36-11-62 | D05528P | = CC | M | | D13944 | | = CC | L | ALL |
| 225B | 18 | VG | XX | | 24-0 | 78-36-21 | D07040P | | | | D04254J | 10 | | | 050-099, 150-156, 162-166, 275-276 |
| 225B | 18 | VG | XX | | 26-0 | 78-36-21 | D07040P | | | | D04254J | 10 | | | 157, 167-199, 277-299 |
| 225R | 18 | VG | XX | | 0-0 | 78-36-21 | D07040P | | | | D04254J | 11 | | | ALL |
| 225Z | | | XX | | 0-0 | 78-36-21 | D07040P | = CC | M | | D04254J | | = CC | M | ALL |
| 226B | 18 | VG | YY | | 24-0 | 78-36-21 | D07040P | | | | D04254J | 12 | | | 050-099, 150-156, 162-166, 275-276 |
| 226B | 18 | VG | YY | | 26-0 | 78-36-21 | D07040P | | | | D04254J | 12 | | | 157, 167-199, 277-299 |
| 226R | 18 | VG | YY | | 0-0 | 78-36-21 | D07040P | | | | D04254J | 13 | | | ALL |
| 226Z | | | YY | | 0-0 | 78-36-21 | D07040P | = CC | M | | D04254J | | = CC | M | ALL |
| 248B | 18 | VG | JV | | 25-0 | 78-36-21 | D07040P | | | | D04254J | 17 | | | 050-099, 150-156, 162-166, 275-276 |
| 248B | 18 | VG | JV | | 26-0 | 78-36-21 | D07040P | | | | D04254J | 17 | | | 157, 167-199, 277-299 |
| 248R | 18 | VG | JV | | 0-0 | 78-36-21 | D07040P | | | | D04254J | 16 | | | ALL |
| 248Z | | | JV | | 0-0 | 78-36-21 | D07040P | = CC | M | | D04254J | | = CC | M | ALL |
| 249B | 18 | VG | JW | | 24-0 | 78-36-21 | D07040P | | | | D04254J | 20 | | | 050-099, 150-156, 162-166, 275-276 |
| 249B | 18 | VG | JW | | 26-0 | 78-36-21 | D07040P | | | | D04254J | 20 | | | 157, 167-199, 277-299 |
| 249R | 18 | VG | JW | | 0-0 | 78-36-21 | D07040P | | | | D04254J | 19 | | | ALL |
| 249Z | | | JW | | 0-0 | 78-36-21 | D07040P | = CC | M | | D04254J | | = CC | M | ALL |
| 301B | 20 | VH | K | | 24-0 | 36-23-21 | D05528P | | | | D04248J | 13 | | | ALL |
| 301R | 20 | VH | K | | 0-0 | 36-23-21 | D05528P | | | | D04248J | 14 | | | ALL |
| 301Y | 20 | VH | K | | 0-0 | 36-23-21 | D05528P | | | | D04248J | 15 | | | ALL |
| 301Z | | | K | | 0-0 | 36-23-21 | D05528P | | | | D04248J | 16 | | | ALL |
| 302B | 20 | VH | M | | 24-0 | 73-31-11 | D04616P | | | | D04252J | 18 | | | ALL |
| 302R | 20 | VH | M | | 0-0 | 73-31-11 | D04616P | | | | D04252J | 17 | | | ALL |
| 302Y | 20 | VH | M | | 0-0 | 73-31-11 | D04616P | | | | D04252J | 19 | | | ALL |
| 302Z | | | M | | 0-0 | 73-31-11 | D04616P | | | | D04252J | | = CC | M | ALL |

WIRE LIST
D280T132

91-21-11
Section W0400
Page 14
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0408 | 286T0408 | | | R WING INBD FS-R2A-HYDRAULICS/ENGINE INSTRUMENTS/FLIGHT CONTROLS (continued) | | | | | | | | | | | | |
| 303B | 20 | VH | MC | 24-0 | 79-31-11 | D04616P | | 1 | | | | D04252J | 12 | | | ALL |
| 303R | 20 | VH | MC | 0-0 | 79-31-11 | D04616P | | 3 | | | | D04252J | 14 | | | ALL |
| 303Y | 20 | VH | MC | 0-0 | 79-31-11 | D04616P | | 2 | | | | D04252J | 13 | | | ALL |
| 303Z | | | MC | 0-0 | 79-31-11 | D04616P | | =CC | M | | | D04252J | =CC | M | | ALL |
| 304B | 20 | VH | MD | 24-0 | 73-33-11 | D04616P | | 49 | | | | D04252J | 29 | | | ALL |
| 304R | 20 | VH | MD | 0-0 | 73-33-11 | D04616P | | 47 | | | | D04252J | 27 | | | ALL |
| 304Y | 20 | VH | MD | 0-0 | 73-33-11 | D04616P | | 48 | | | | D04252J | 28 | | | ALL |
| 304Z | | | MD | 0-0 | 73-33-11 | D04616P | | =CC | M | | | D04252J | =CC | M | | ALL |
| FRA | | | | 0-0 | 29-33-11 | D04170P | | | | FA | | D04170P | 4 | | | ALL |
| FRB | | | | 0-0 | 29-33-11 | D04170P | | | | FA | | D04170P | 11 | | | ALL |
| FRC | | | | 0-0 | 29-33-11 | D04170P | | | | FA | | D04170P | 13 | | | ALL |
| FRD | | | | 0-0 | 29-33-11 | D05528P | | | | FB | | D05528P | 28 | | | ALL |
| FRE | | | | 0-0 | 29-33-11 | D05528P | | | | FB | | D05528P | 29 | | | ALL |
| FRF | | | | 0-0 | 29-33-11 | D05528P | | | | FB | | D05528P | 48 | | | ALL |
| W0409 | 286T0409 | | | P51 TO E1-SHELF-S2 | | | | | | | | | | | | |
| 001 | 24 | PK | | 22-0 | SPARE | D04301P | | 1 | | | | D04305J | 1 | | | ALL |
| 005 | 24 | PK | | 22-0 | 31-51-12 | D04301P | | 5 | | | | D04305J | 5 | | | ALL |
| 006 | 20 | PA | | 10-0 | 27-32-11 | D04301P | | 6 | | | | SP00223 | | 9 | | ALL |
| 007 | 24 | PK | | 22-0 | SPARE | D04301P | | 7 | | | | D04305J | 7 | | | 050-099 |
| 011 | 24 | PK | | 22-0 | 22-14-11 | D04301P | | 11 | | | | D04305J | 11 | | | ALL |
| 012 | 20 | PA | | 3-0 | 31-51-12 | D04301P | | 4 | | | | GD00301 | A.. | 2 | | ALL |
| 201B | 24 | PW | IA | 22-0 | SPARE | D04301P | | 2 | | | | D04305J | 2 | | | ALL |
| 201R | 24 | PW | IA | 0-0 | SPARE | D04301P | | 3 | | | | D04305J | 3 | | | ALL |
| 201Z | | | IA | 0-0 | SPARE | D04301P | | 12 | | | | D04305J | 12 | | | ALL |
| 202B | 24 | PW | IB | 22-0 | SPARE | D04301P | | 14 | | | | D04305J | 14 | | | 050-099 |
| 202R | 24 | PW | IB | 0-0 | SPARE | D04301P | | 13 | | | | D04305J | 13 | | | 050-099 |
| 202Z | | | IB | 0-0 | SPARE | D04301P | | 15 | | | | D04305J | 15 | | | 050-099 |
| 203 | 20 | UA | | 3-0 | 34-16-11 | D04301P | | | | IC | | GD00301 | S.. | 2 | | ALL |
| 203B | 24 | PW | IC | 22-0 | 34-16-11 | D04301P | | 9 | | | | D04305J | 9 | | | ALL |
| 203R | 24 | PW | IC | 0-0 | 34-16-11 | D04301P | | 8 | | | | D04305J | 8 | | | ALL |
| 203Z | | | IC | 0-0 | 34-16-11 | D04301P | | | | IC | | D04305J | 10 | | | ALL |
| 266B | 24 | PW | KP | 22-0 | 32-45-11 | D04301P | | 17 | | | | D04305J | 17 | | | 050-099, 150-199 |
| 266R | 24 | PW | KP | 0-0 | 32-45-11 | D04301P | | 16 | | | | D04305J | 16 | | | 050-099, 150-199 |
| 266Z | | | KP | 0-0 | 32-45-11 | D04301P | | 18 | | | | D04305J | 18 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0400

Page 15 End

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0410 | 286T0410 | | | P32 TO F4- L FWD GALLEY POWER FEEDER | | | | | | | | | | | |
| 001 | 06 | | QY | | 39-5 | 25-31-12 | M01618 | A2 | H6 | | SM00001 | | GE | | 050-099, 150-199 |
| 002 | 06 | | QY | | 39-5 | 25-31-12 | M01618 | B2 | H6 | | SM00002 | | GE | | 050-099, 150-199 |
| 003 | 06 | | QY | | 39-5 | 25-31-12 | M01618 | C2 | H6 | | SM00003 | | GE | | 050-099, 150-199 |
| 004 | 08 | | HA | | 8-9 | 25-31-12 | D13448 | | A | | SM00001 | | GE | | 050-099, 150-199 |
| 005 | 08 | | HA | | 8-9 | 25-31-12 | D13448 | | B | | SM00002 | | GE | | 050-099, 150-199 |
| 006 | 08 | | HA | | 8-9 | 25-31-12 | D13448 | | C | | SM00003 | | GE | | 050-099, 150-199 |
| 007 | 08 | | HA | | 2-7 | 25-31-12 | D13448 | | D | | GD05622 | A.. | G | | 050-099, 150-199 |
| W0411 | 286T0411 | | | PACS STAB. & FLAP POS MODULE C,P50 TO SHELF | | | | | | | | | | | |
| 001 | 22 | | PA | | 20-0 | 22-24-11 | D04881J | | 1 | | D04885P | | 1 | | ALL |
| 004 | 24 | | PK | | 20-0 | SPARE | D04881J | | 4 | | D04885P | | 4 | | ALL |
| 005 | 22 | | PA | | 20-0 | 27-61-11 | D04881J | | 5 | | D04885P | | 5 | | ALL |
| 006 | 24 | | PK | | 20-0 | 22-12-31 | D04881J | | 6 | | D04885P | | 6 | | ALL |
| 007 | 24 | | PK | | 20-0 | 22-12-31 | D04881J | | 7 | | D04885P | | 7 | | ALL |
| 008 | 24 | | PK | | 20-0 | 22-12-31 | D04881J | | 8 | | D04885P | | 8 | | ALL |
| 009 | 24 | | PK | | 20-0 | 22-12-31 | D04881J | | 9 | | D04885P | | 9 | | ALL |
| 010 | 22 | | PA | | 20-0 | SPARE | D04881J | | 10 | | D04885P | | 10 | | ALL |
| 203B | 24 | | PL | IC | 20-0 | 27-32-11 | D04881J | | 3 | | D04885P | | 3 | | ALL |
| 203R | 24 | | PL | IC | 0-0 | 27-32-11 | D04881J | | 2 | | D04885P | | 2 | | ALL |
| W0412 | 286T0412 | | | L WING-L2-IDG CONTROL | | | | | | | | | | | |
| 001 | 18 | | VF | H | 23-6 | 24-11-11 | D04342J | | 4 | | D04398P | | 4 | | ALL |
| 001Z | | | | H | 0-0 | 24-11-11 | D04342J | | DED | | D04398P | | DED | | ALL |
| 002 | 20 | | UA | | 23-5 | 24-11-11 | D04342J | | 21 | | D06586P | | 1 | | ALL |
| 003 | 20 | | UA | | 23-7 | 24-11-11 | D04342J | | 16 | | D04550P | | 16 | | ALL |
| 005 | 18 | | UA | | 23-6 | SPARE | D04342J | | 26 | | D04398P | | 5 | | ALL |
| 006 | 20 | | UA | | 23-5 | 24-11-11 | D04342J | | 22 | | D06586P | | 2 | | ALL |
| 007 | 20 | | UA | | 23-5 | 24-11-11 | D04342J | | 27 | | D06586P | | 3 | | ALL |
| 008 | 20 | | UA | | 23-5 | 24-11-11 | D04342J | | 28 | | D06586P | | 4 | | ALL |
| 201B | 20 | | VG | A | 23-7 | 24-11-11 | D04342J | | 1 | | D04550P | | 1 | | ALL |
| 201R | 20 | | VG | A | 0-0 | 24-11-11 | D04342J | | 2 | | D04550P | | 2 | | ALL |
| 201Z | | | | A | 0-0 | 24-11-11 | D04342J | | 3 | | D04550P | | 3 | | ALL |
| 202B | 20 | | VG | B | 23-7 | 24-21-11 | D04342J | | 5 | | D04550P | | 5 | | ALL |
| 202R | 20 | | VG | B | 0-0 | 24-21-11 | D04342J | | 6 | | D04550P | | 6 | | ALL |
| 202Z | | | | B | 0-0 | 24-21-11 | D04342J | | 7 | | D04550P | | 7 | | ALL |
| 203B | 20 | | UB | D | 23-7 | 24-11-11 | D04342J | | 12 | | D04550P | | 12 | | ALL |
| 203R | 20 | | UB | D | 0-0 | 24-11-11 | D04342J | | 13 | | D04550P | | 13 | | ALL |
| 204B | 20 | | UB | E | 23-7 | 24-11-11 | D04342J | | 14 | | D04550P | | 14 | | ALL |
| 204R | 20 | | UB | E | 0-0 | 24-11-11 | D04342J | | 15 | | D04550P | | 15 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0410
 Page 1
 Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0412 | 286T0412 | | | L WING-L2-IDG CONTROL (continued) | | | | | | | | | | | |
| 301B | 18 | UC | F | 23-6 | 24-21-11 | D04342J | 18 | | | D04398P | 1 | | | ALL | |
| 301R | 18 | UC | F | 0-0 | 24-21-11 | D04342J | 19 | | | D04398P | 2 | | | ALL | |
| 301Y | 18 | UC | F | 0-0 | 24-21-11 | D04342J | 20 | | | D04398P | 3 | | | ALL | |
| 401B | 20 | UD | C | 23-7 | 24-21-11 | D04342J | 8 | | | D04550P | 8 | | | ALL | |
| 401G | 20 | UD | C | 0-0 | 24-21-11 | D04342J | 11 | | | D04550P | 11 | | | ALL | |
| 401R | 20 | UD | C | 0-0 | 24-21-11 | D04342J | 9 | | | D04550P | 9 | | | ALL | |
| 401Y | 20 | UD | C | 0-0 | 24-21-11 | D04342J | 10 | | | D04550P | 10 | | | ALL | |
| W0413 | 286T0413 | | | PACS STAB. & FLAP POS MODULE R,P50 TO SHELF | | | | | | | | | | | |
| 001 | 22 | PA | | 23-7 | 22-24-21 | D04883J | 1 | | | D04887P | 1 | | | ALL | |
| 006 | 24 | PK | | 23-7 | 22-12-21 | D04883J | 6 | | | D04887P | 6 | | | ALL | |
| 007 | 24 | PK | | 23-7 | 22-12-21 | D04883J | 7 | | | D04887P | 7 | | | ALL | |
| 008 | 24 | PK | | 23-7 | 22-12-21 | D04883J | 8 | | | D04887P | 8 | | | ALL | |
| 009 | 24 | PK | | 23-7 | 22-12-21 | D04883J | 9 | | | D04887P | 9 | | | ALL | |
| 010 | 22 | PA | | 23-7 | SPARE | D04883J | 10 | | | D04887P | 10 | | | ALL | |
| 011 | 24 | PK | | 23-5 | 22-32-13 | D04895J | 1 | | | D04887P | 11 | | | ALL | |
| 012 | 24 | PK | | 23-5 | 22-32-13 | D04895J | 2 | | | D04887P | 12 | | | ALL | |
| 013 | 24 | PK | | 23-5 | SPARE | D04895J | 3 | | | D04887P | 13 | | | ALL | |
| 014 | 24 | PK | | 23-5 | 22-32-13 | D04895J | 4 | | | D04887P | 14 | | | ALL | |
| 015 | 24 | PK | | 23-5 | 22-32-13 | D04895J | 5 | | | D04887P | 15 | | | ALL | |
| 016 | 24 | PK | | 23-5 | 22-32-13 | D04895J | 6 | | | D04887P | 16 | | | ALL | |
| 017 | 24 | PK | | 23-5 | 22-32-13 | D04895J | 7 | | | D04887P | 17 | | | ALL | |
| 018 | 24 | PK | | 23-5 | 22-32-13 | D04895J | 8 | | | D04887P | 18 | | | ALL | |
| 020 | 22 | PA | | 23-7 | 27-41-21 | D04883J | 16 | | | D04887P | 26 | | | 050-099 | |
| 020 | 24 | PK | | 23-7 | 27-41-21 | D04883J | 16 | | | D04887P | 26 | | | 150-199, 275-299 | |
| 023 | 22 | PA | | 23-7 | 27-61-11 | D04883J | 17 | | | D04887P | 27 | | | ALL | |
| 034 | 24 | PK | | 23-7 | SPARE | D04883J | 21 | | | D04887P | 40 | | | ALL | |
| 201B | 22 | PB | IA | 23-7 | 27-41-21 | D04883J | 5 | | | D04887P | 5 | | | ALL | |
| 201R | 22 | PB | IA | 0-0 | 27-41-21 | D04883J | 4 | | | D04887P | 4 | | | ALL | |
| 204B | 24 | PL | ID | 23-7 | 27-58-21 | D04883J | 25 | | | D04887P | 30 | | | ALL | |
| 204R | 24 | PL | ID | 0-0 | 27-58-21 | D04883J | 26 | | | D04887P | 31 | | | ALL | |
| 205B | 24 | PL | IE | 23-7 | 27-32-21 | D04883J | 23 | | | D04887P | 29 | | | ALL | |
| 205R | 24 | PL | IE | 0-0 | 27-32-21 | D04883J | 22 | | | D04887P | 28 | | | ALL | |
| 206B | 24 | PL | IF | 23-7 | SPARE | D04883J | 19 | | | D04887P | 19 | | | ALL | |
| 206R | 24 | PL | IF | 0-0 | SPARE | D04883J | 20 | | | D04887P | 20 | | | ALL | |
| 301B | 24 | PM | MA | 23-7 | 27-58-21 | D04883J | 27 | | | D04887P | 32 | | | ALL | |
| 301R | 24 | PM | MA | 0-0 | 27-58-21 | D04883J | 28 | | | D04887P | 33 | | | ALL | |
| 301Y | 24 | PM | MA | 0-0 | 27-58-21 | D04883J | 29 | | | D04887P | 34 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0410

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|---------|-------|------|-------|---------|-------|-------|------|--------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0414 | 286T0414 | | | R WING-R2-IDG CONTROL | | | | | | | | | | | |
| 001 | 18 | VF | H | 22-4 | 24-11-21 | D04344J | | 4 | | D04400P | | 4 | | ALL | |
| 001Z | | | H | 0-0 | 24-11-21 | D04344J | | | DED | D04400P | | DED | | ALL | |
| 002 | 20 | UA | | 23-5 | 24-11-21 | D04344J | | 21 | | D06588P | | 1 | | ALL | |
| 003 | 20 | UA | | 22-6 | 24-11-21 | D04344J | | 16 | | D04630P | | 16 | | ALL | |
| 005 | 18 | UA | | 22-4 | SPARE | D04344J | | 26 | | D04400P | | 5 | | ALL | |
| 006 | 20 | UA | | 23-5 | 24-11-21 | D04344J | | 22 | | D06588P | | 2 | | ALL | |
| 007 | 20 | UA | | 23-5 | 24-11-21 | D04344J | | 27 | | D06588P | | 3 | | ALL | |
| 008 | 20 | UA | | 23-5 | 24-11-21 | D04344J | | 28 | | D06588P | | 4 | | ALL | |
| 201B | 20 | VG | A | 22-6 | 24-11-21 | D04344J | | 1 | | D04630P | | 1 | | ALL | |
| 201R | 20 | VG | A | 0-0 | 24-11-21 | D04344J | | 2 | | D04630P | | 2 | | ALL | |
| 201Z | | | A | 0-0 | 24-11-21 | D04344J | | 3 | | D04630P | | 3 | | ALL | |
| 202B | 20 | VG | B | 22-6 | 24-21-21 | D04344J | | 5 | | D04630P | | 5 | | ALL | |
| 202R | 20 | VG | B | 0-0 | 24-21-21 | D04344J | | 6 | | D04630P | | 6 | | ALL | |
| 202Z | | | B | 0-0 | 24-21-21 | D04344J | | 7 | | D04630P | | 7 | | ALL | |
| 203B | 20 | UB | D | 22-6 | 24-11-21 | D04344J | | 12 | | D04630P | | 12 | | ALL | |
| 203R | 20 | UB | D | 0-0 | 24-11-21 | D04344J | | 13 | | D04630P | | 13 | | ALL | |
| 204B | 20 | UB | E | 22-6 | 24-11-21 | D04344J | | 14 | | D04630P | | 14 | | ALL | |
| 204R | 20 | UB | E | 0-0 | 24-11-21 | D04344J | | 15 | | D04630P | | 15 | | ALL | |
| 205B | 20 | VG | G | 22-6 | SPARE | D04344J | | 23 | | D04630P | | 23 | | ALL | |
| 205R | 20 | VG | G | 0-0 | SPARE | D04344J | | 24 | | D04630P | | 24 | | ALL | |
| 205Z | | | G | 0-0 | SPARE | D04344J | | 25 | | D04630P | | 4 | | ALL | |
| 301B | 18 | UC | F | 22-4 | 24-21-21 | D04344J | | 18 | | D04400P | | 1 | | ALL | |
| 301R | 18 | UC | F | 0-0 | 24-21-21 | D04344J | | 19 | | D04400P | | 2 | | ALL | |
| 301Y | 18 | UC | F | 0-0 | 24-21-21 | D04344J | | 20 | | D04400P | | 3 | | ALL | |
| 401B | 20 | UD | C | 22-6 | 24-21-21 | D04344J | | 8 | | D04630P | | 8 | | ALL | |
| 401G | 20 | UD | C | 0-0 | 24-21-21 | D04344J | | 11 | | D04630P | | 11 | | ALL | |
| 401R | 20 | UD | C | 0-0 | 24-21-21 | D04344J | | 9 | | D04630P | | 9 | | ALL | |
| 401Y | 20 | UD | C | 0-0 | 24-21-21 | D04344J | | 10 | | D04630P | | 10 | | ALL | |
| W0416 | 286T0416 | | | L WING INBD FS-L2B-ENG INSTR A | | | | | | | | | | | |
| 002 | 20 | VF | AB | 23-8 | 73-34-11 | D04202J | | 2 | | D04524P | | 2 | | ALL | |
| 002Z | | | AB | 0-0 | 73-34-11 | D04202J | | | =CC M | D04524P | | =CC M | | ALL | |
| 009 | 18 | UA | | 23-8 | 29-11-11 | D04202J | | 9 | | D04524P | | 9 | DL | ALL | |
| 011 | 18 | UA | | 23-8 | SPARE | D04202J | | 1 | | D04524P | | 18 | DL | ALL | |
| 012 | 20 | UA | | 23-8 | 74-31-11 | D04202J | | 12 | | D04524P | | 12 | | ALL | |
| 023 | 20 | UA | | 23-8 | SPARE | D04202J | | | CAP Y | D04524P | | 21 | | ALL | |
| 038 | 18 | UA | | 23-8 | 36-11-61 | D04524P | | 42 | DL | D04202J | | 3 | | ALL | |
| 039 | 18 | UA | | 23-8 | 36-11-61 | D04524P | | 43 | DL | D04202J | | 4 | | ALL | |
| 040 | 20 | UA | | 23-8 | 36-11-61 | D04524P | | 44 | | D04202J | | 21 | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W0410
Page 3
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|--|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0416 | 286T0416 | | | L WING INBD FS-L2B-ENG INSTR A (continued) | | | | | | | | | | | | | | |
| 103 | 20 | | UA | 23-8 | 36-11-61 | D04524P | | 30 | | | | | D04202J | | 38 | | | ALL |
| 104 | 20 | | UA | 23-8 | 36-11-61 | D04524P | | 31 | | | | | D04202J | | 40 | | | ALL |
| 105 | 20 | | UA | 23-8 | 36-11-61 | D04524P | | 32 | | | | | D04202J | | 42 | | | ALL |
| 106 | 18 | | VF | EF | 23-8 | 78-34-11 | D04202J | | 36 | | | | D04524P | | 45 | DL | | ALL |
| 106Z | | | | EF | 0-0 | 78-34-11 | D04202J | =CC | | M | | | D04524P | =CC | | M | | ALL |
| 107 | 18 | | VF | EG | 23-8 | 78-34-11 | D04202J | | 37 | | | | D04524P | | 46 | DL | | ALL |
| 107Z | | | | EG | 0-0 | 78-34-11 | D04202J | =CC | | M | | | D04524P | =CC | | M | | ALL |
| 108 | 18 | | VF | EH | 23-8 | 78-34-11 | D04202J | | 34 | | | | D04524P | | 33 | DL | | ALL |
| 108Z | | | | EH | 0-0 | 78-34-11 | D04202J | =CC | | M | | | D04524P | =CC | | M | | ALL |
| 110 | 18 | | VF | EJ | 23-8 | 78-34-11 | D04202J | | 5 | | | | D04524P | | 47 | DL | | ALL |
| 110Z | | | | EJ | 0-0 | 78-34-11 | D04202J | =CC | | M | | | D04524P | =CC | | M | | ALL |
| 111 | 18 | | VF | EK | 23-8 | 78-34-11 | D04202J | | 6 | | | | D04524P | | 48 | DL | | ALL |
| 111Z | | | | EK | 0-0 | 78-34-11 | D04202J | =CC | | M | | | D04524P | =CC | | M | | ALL |
| 201B | 20 | | UB | IA | 23-8 | 78-34-11 | D04202J | | 23 | | | | D04524P | | 23 | | | ALL |
| 201R | 20 | | UB | IA | 0-0 | 78-34-11 | D04202J | | 24 | | | | D04524P | | 24 | | | ALL |
| 202B | 20 | | UB | IB | 23-8 | 78-34-11 | D04202J | | 25 | | | | D04524P | | 25 | | | ALL |
| 202R | 20 | | UB | IB | 0-0 | 78-34-11 | D04202J | | 26 | | | | D04524P | | 26 | | | ALL |
| 205B | 20 | | UB | G | 23-8 | SPARE | D04202J | | 32 | | | | D04524P | | 36 | | | ALL |
| 205R | 20 | | UB | G | 0-0 | SPARE | D04202J | | 33 | | | | D04524P | | 22 | | | ALL |
| 303B | 20 | | VH | MC | 23-8 | 79-32-11 | D04202J | | 15 | | | | D04524P | | 15 | | | ALL |
| 303R | 20 | | VH | MC | 0-0 | 79-32-11 | D04202J | | 13 | | | | D04524P | | 13 | | | ALL |
| 303Y | 20 | | VH | MC | 0-0 | 79-32-11 | D04202J | | 14 | | | | D04524P | | 14 | | | ALL |
| 303Z | | | | MC | 0-0 | 79-32-11 | D04202J | =CC | | M | | | D04524P | =CC | | M | | ALL |
| W0417 | 286T0417 | | | WARNING & ANN,EFIS,P3 TO SHELF | | | | | | | | | | | | | | |
| 001 | 24 | | PK | 34-0 | 34-22-27 | D04393J | | 4 | | | | | D04391J | | 4 | | | ALL |
| 002 | 24 | | PK | 34-0 | 34-22-27 | D04393J | | 5 | | | | | D04391J | | 5 | | | ALL |
| 003 | 24 | | PK | 34-0 | 34-22-27 | D04393J | | 6 | | | | | D04391J | | 6 | | | ALL |
| 005 | 24 | | PK | 34-0 | 34-22-27 | D04393J | | 11 | | | | | D04391J | | 11 | | | ALL |
| 007 | 24 | | PK | 34-0 | 22-14-21 | D04393J | | 13 | | | | | D04391J | | 13 | | | ALL |
| 008 | 24 | | PK | 34-0 | 22-14-21 | D04393J | | 14 | | | | | D04391J | | 14 | | | ALL |
| 009 | 24 | | PK | 34-0 | 22-14-21 | D04393J | | 15 | | | | | D04391J | | 15 | | | ALL |
| 010 | 22 | | PA | 34-0 | 22-14-21 | D04393J | | 17 | | | | | D04391J | | 17 | | | ALL |
| 011 | 24 | | PK | 34-0 | 34-22-37 | D04393J | | 30 | | | | | D04391J | | 30 | | | ALL |
| 015 | 24 | | PK | 34-0 | 22-41-13 | D04393J | | 35 | | | | | D04391J | | 35 | | | ALL |
| 016 | 22 | | PA | 34-0 | 34-22-26 | D04393J | | 16 | | | | | D04391J | | 16 | | | ALL |
| 017 | 24 | | PK | 34-0 | 22-41-13 | D04393J | | 37 | | | | | D04391J | | 37 | | | ALL |
| 018 | 24 | | PK | 34-0 | 22-41-13 | D04393J | | 36 | | | | | D04391J | | 36 | | | ALL |
| 022 | 24 | | PK | 34-0 | 34-22-27 | D04391J | | 31 | | | | | D04393J | | 31 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0410

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0417 | 286T0417 | | | WARNING & ANN,EFIS,P3 TO SHELF (continued) | | | | | | | | | | | |
| 024 | 22 | | PA | 34-0 | 34-22-27 | D04391J | | 44 | | | D04393J | | 44 | | ALL |
| 025 | 22 | | PA | 34-0 | 34-227 | D04393J | | 12 | | | D04391J | | 12 | | ALL |
| 201 | 20 | | UA | 1-6 | 34-22-92 | GD00553 | | S.. | 2 | | D04391J | | | FA | ALL |
| 201B | 24 | | PW | IA | 34-0 | 34-22-92 | D04393J | | 2 | | D04391J | | 2 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-22-92 | D04393J | | 1 | | D04391J | | 1 | | ALL |
| 201Z | | | IA | 0-0 | 34-22-92 | D04393J | | 3 | | | D04391J | | | FA | ALL |
| 202B | 24 | | PW | IB | 34-0 | SPARE | D04393J | | 9 | | D04391J | | 9 | | ALL |
| 202R | 24 | | PW | IB | 0-0 | SPARE | D04393J | | 8 | | D04391J | | 8 | | ALL |
| 202Z | | | IB | 0-0 | SPARE | D04393J | | 10 | | | D04391J | | 10 | | ALL |
| 206B | 22 | | PR | IF | 34-0 | SPARE | D04393J | | 28 | | D04391J | | 28 | | ALL |
| 206R | 22 | | PR | IF | 0-0 | SPARE | D04393J | | 27 | | D04391J | | 27 | | ALL |
| 206Z | | | IF | 0-0 | SPARE | D04393J | | 29 | | | D04391J | | 29 | | ALL |
| 301B | 24 | | PM | MA | 34-0 | 34-12-11 | D04391J | | 33 | | D04393J | | 33 | | ALL |
| 301R | 24 | | PM | MA | 0-0 | 34-12-11 | D04391J | | 32 | | D04393J | | 32 | | ALL |
| 301Y | 24 | | PM | MA | 0-0 | 34-12-11 | D04391J | | 34 | | D04393J | | 34 | | ALL |
| FRA | | | | 0-0 | 34-22-92 | D04391J | | | | FA | D04391J | | 3 | | ALL |
| W0418 | 286T0418 | | | R WING-R2B-ENG INSTR/ANTI-ICE/SLATS/HYDRAULICS | | | | | | | | | | | |
| 002 | 20 | | VF | AB | 24-0 | 73-34-11 | D04242J | | 2 | | D04622P | | 2 | | 050-099, 150-199 |
| 002 | 20 | | VF | AB | 23-1 | 73-34-11 | D04242J | | 2 | | D04622P | | 2 | | 275-299 |
| 002Z | | | | AB | 0-0 | 73-34-11 | D04242J | | = CC | M | D04622P | | = CC | M | ALL |
| 009 | 20 | | UA | | 24-0 | 29-11-21 | D04242J | | 9 | | D04622P | | 9 | | 050-099, 150-199 |
| 009 | 20 | | UA | | 23-1 | 29-11-21 | D04242J | | 9 | | D04622P | | 9 | | 275-299 |
| 011 | 18 | | UA | | 24-0 | SPARE | D04622P | | 18 | DL | D04242J | | 1 | | 050-099, 150-199 |
| 011 | 18 | | UA | | 23-1 | SPARE | D04622P | | 18 | DL | D04242J | | 1 | | 275-299 |
| 012 | 20 | | UA | | 24-0 | 74-31-21 | D04242J | | 12 | | D04622P | | 12 | | 050-099, 150-199 |
| 012 | 20 | | UA | | 23-1 | 74-31-21 | D04242J | | 12 | | D04622P | | 12 | | 275-299 |
| 023 | 20 | | UA | | 24-0 | SPARE | D04242J | | 41 | | D04622P | | 21 | | 050-099, 150-199 |
| 023 | 20 | | UA | | 23-1 | SPARE | D04242J | | 41 | | D04622P | | 21 | | 275-299 |
| 027 | 20 | | UA | | 31-0 | SPARE | D04380P | | 2 | | D05598P | | 1 | | 150-199 |
| 027 | 20 | | UA | | 30-4 | 30-11-11 | D04380P | | 2 | | D05598P | | 1 | | 275-299 |
| 028 | 20 | | UA | | 31-0 | 30-11-11 | D04380P | | 1 | | D05598P | | 2 | | 050-099, 150-199 |
| 028 | 20 | | UA | | 30-4 | 30-11-11 | D04380P | | 1 | | D05598P | | 2 | | 275-299 |
| 029 | 20 | | UA | | 31-0 | 33-43-11 | D05598P | | 4 | | D04380P | | 4 | | 050-099 |
| 029 | 20 | | UA | | 31-0 | 33-43-11 | D05598P | | 3 | | D04380P | | 4 | | 150-199 |
| 029 | 20 | | UA | | 30-4 | 33-43-11 | D05598P | | 3 | | D04380P | | 4 | | 275-299 |
| 031 | 18 | | UA | | 31-0 | 33-44-21 | D04380P | | 6 | | D05598P | | 6 | DL | 050-099, 150-199 |
| 031 | 18 | | UA | | 30-4 | 33-44-21 | D04380P | | 6 | | D05598P | | 6 | DL | 275-299 |
| 032 | 20 | | UA | | 31-0 | SPARE | D04380P | | 3 | | D05598P | | 7 | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0410
Page 5
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0418 | 286T0418 | | | R WING-R2B-ENG INSTR/ANTI-ICE/SLATS/HYDRAULICS (continued) | | | | | | | | | | | | | | |
| 032 | 20 | | UA | 30-4 | 30-11-11 | D04380P | | 3 | | | | | D05598P | | 7 | | | 275-299 |
| 037 | 20 | | UA | 31-0 | 30-11-11 | D01596 | | 1 | | | | | D05598P | | 8 | | | 050-099, 150-199 |
| 037 | 20 | | UA | 30-8 | 30-11-11 | D01596 | | 1 | | | | | D05598P | | 8 | | | 275-299 |
| 038 | 18 | | UA | 3-0 | 30-11-11 | D01596 | | 2 | | | | | GD02474 | D.. | N | | | 050-099, 150-199 |
| 038 | 18 | | UA | 1-8 | 30-11-11 | D01596 | | 2 | | | | | GD02474 | D.. | N | | | 275-299 |
| 039 | 20 | | UA | 31-0 | 30-11-11 | D01596 | | 4 | | | | | D05598P | | 10 | | | 050-099, 150-199 |
| 039 | 20 | | UA | 30-8 | 30-11-11 | D01596 | | 4 | | | | | D05598P | | 10 | | | 275-299 |
| 040 | 20 | | UA | 31-0 | 30-11-11 | D01596 | | 5 | | | | | D05598P | | 11 | | | 050-099, 150-199 |
| 040 | 20 | | UA | 30-8 | 30-11-11 | D01596 | | 5 | | | | | D05598P | | 11 | | | 275-299 |
| 041 | 18 | | UA | 3-0 | 30-11-11 | D01596 | | 3 | | | | | GD02474 | D.. | N | | | 050-099, 150-199 |
| 041 | 18 | | UA | 1-8 | 30-11-11 | D01596 | | 3 | | | | | GD02474 | D.. | N | | | 275-299 |
| 042 | 18 | | UA | 3-0 | 30-11-11 | D01596 | | 6 | | | | | GD03044 | S.. | N | | | 050-099, 150-199 |
| 042 | 18 | | UA | 1-10 | 30-11-11 | D01596 | | 6 | | | | | GD03044 | S.. | N | | | 275-299 |
| 043 | 20 | | UA | 10-0 | 27-81-11 | D01516 | | 2 | | | | | D05712P | | 1 | | | 050-099, 150-199 |
| 043 | 20 | | UA | 9-6 | 27-81-11 | D01516 | | 2 | | | | | D05712P | | 1 | | | 275-299 |
| 044 | 18 | | UA | 10-0 | 27-81-11 | D01516 | | 3 | | | | | D05712P | | 2 | DL | | 050-099, 150-199 |
| 044 | 18 | | UA | 9-6 | 27-81-11 | D01516 | | 3 | | | | | D05712P | | 2 | DL | | 275-299 |
| 045 | 18 | | UA | 10-0 | 27-81-11 | D01516 | | 5 | | | | | D05712P | | 3 | DL | | 050-099, 150-199 |
| 045 | 18 | | UA | 9-6 | 27-81-11 | D01516 | | 5 | | | | | D05712P | | 3 | DL | | 275-299 |
| 046 | 18 | | UA | 3-0 | 27-81-11 | D01516 | | 1 | | | | | GD02472 | D.. | N | | | 050-099, 150-199 |
| 046 | 18 | | UA | 2-3 | 27-81-11 | D01516 | | 1 | | | | | GD02472 | D.. | N | | | 275-299 |
| 047 | 18 | | UA | 3-0 | 27-81-11 | D01516 | | 8 | | | | | GD03042 | S.. | N | | | 050-099, 150-199 |
| 047 | 18 | | UA | 2-4 | 27-81-11 | D01516 | | 8 | | | | | GD03042 | S.. | N | | | 275-299 |
| 048 | 18 | | UA | 4-0 | 27-81-11 | D02294 | | 6 | | | | | GD02470 | S.. | N | | | 050-099, 150-199 |
| 048 | 18 | | UA | 2-8 | 27-81-11 | D02294 | | 6 | | | | | GD02470 | S.. | N | | | 275-299 |
| 058 | 18 | | UA | 24-0 | 36-11-62 | D05598P | | 24 | DL | | | | D04242J | | 3 | | | 050-099, 150-199 |
| 058 | 18 | | UA | 23-5 | 36-11-62 | D05598P | | 24 | DL | | | | D04242J | | 3 | | | 275-299 |
| 059 | 18 | | UA | 24-0 | 36-11-62 | D05598P | | 25 | DL | | | | D04242J | | 4 | | | 050-099, 150-199 |
| 059 | 18 | | UA | 23-5 | 36-11-62 | D05598P | | 25 | DL | | | | D04242J | | 4 | | | 275-299 |
| 060 | 20 | | UA | 24-0 | 36-11-62 | D05598P | | 23 | | | | | D04242J | | 21 | | | 050-099, 150-199 |
| 060 | 20 | | UA | 23-5 | 36-11-62 | D05598P | | 23 | | | | | D04242J | | 21 | | | 275-299 |
| 103 | 20 | | UA | 25-0 | 36-11-62 | D05598P | | 17 | | | | | D04242J | | 38 | | | 050-099, 150-155, 162-165 |
| 103 | 20 | | UA | 24-0 | 36-11-62 | D05598P | | 17 | | | | | D04242J | | 38 | | | 156-157, 166-199 |
| 103 | 20 | | UA | 23-5 | 36-11-62 | D05598P | | 17 | | | | | D04242J | | 38 | | | 275-299 |
| 104 | 20 | | UA | 25-0 | 36-11-62 | D05598P | | 18 | | | | | D04242J | | 40 | | | 050-099, 150-155, 162-165 |
| 104 | 20 | | UA | 24-0 | 36-11-62 | D05598P | | 18 | | | | | D04242J | | 40 | | | 156-157, 166-199 |
| 104 | 20 | | UA | 23-5 | 36-11-62 | D05598P | | 18 | | | | | D04242J | | 40 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0410

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0418 | 286T0418 | | | R WING-R2B-ENG INSTR/ANTI-ICE/SLATS/HYDRAULICS (continued) | | | | | | | | | | | |
| 105 | 20 | | UA | 25-0 | 36-11-62 | D05598P | | 19 | | | D04242J | | 42 | | 050-099, 150-155, 162-165 |
| 105 | 20 | | UA | 24-0 | 36-11-62 | D05598P | | 19 | | | D04242J | | 42 | | 156-157, 166-199 |
| 105 | 20 | | UA | 23-5 | 36-11-62 | D05598P | | 19 | | | D04242J | | 42 | | 275-299 |
| 106 | 18 | | VF EF | 30-0 | 78-34-21 | D05712P | | 9 | DL | | D04242J | | 35 | | 050-099, 150-199 |
| 106 | 18 | | VF EF | 23-2 | 78-34-21 | D05712P | | 9 | DL | | D04242J | | 35 | | 275-299 |
| 106Z | | | EF | 0-0 | 78-34-21 | D05712P | | =CC | L | | D04242J | | =CC | M | ALL |
| 107 | 18 | | VF EG | 30-0 | 78-34-21 | D05712P | | 10 | DL | | D04242J | | 36 | | 050-099, 150-199 |
| 107 | 18 | | VF EG | 23-2 | 78-34-21 | D05712P | | 10 | DL | | D04242J | | 36 | | 275-299 |
| 107Z | | | EG | 0-0 | 78-34-21 | D05712P | | =CC | L | | D04242J | | =CC | M | ALL |
| 108 | 18 | | VF EH | 25-0 | 78-34-21 | D04622P | | 49 | DL | | D04242J | | 34 | | 050-099, 150-156, 162-166 |
| 108 | 18 | | VF EH | 30-0 | 78-34-21 | D04622P | | 47 | DL | | D04242J | | 34 | | 157 |
| 108 | 18 | | VF EH | 30-0 | 78-34-21 | D04622P | | 49 | DL | | D04242J | | 34 | | 167-199 |
| 108 | 18 | | VF EH | 23-1 | 78-34-21 | D04622P | | 49 | DL | | D04242J | | 34 | | 275-278 |
| 108 | 18 | | VF EH | 23-1 | 78-34-21 | D04622P | | 47 | DL | | D04242J | | 34 | | 280-299 |
| 108Z | | | EH | 0-0 | 78-34-21 | D04622P | | =CC | M | | D04242J | | =CC | M | ALL |
| 110 | 18 | | VF EJ | 30-0 | 78-34-21 | D05712P | | 11 | DL | | D04242J | | 5 | | 050-099, 150-199 |
| 110 | 18 | | VF EJ | 23-2 | 78-34-21 | D05712P | | 11 | DL | | D04242J | | 5 | | 275-299 |
| 110Z | | | EJ | 0-0 | 78-34-21 | D05712P | | =CC | L | | D04242J | | =CC | M | ALL |
| 111 | 18 | | VF EK | 30-0 | 78-34-21 | D05712P | | 12 | DL | | D04242J | | 6 | | 050-099, 150-199 |
| 111 | 18 | | VF EK | 23-2 | 78-34-21 | D05712P | | 12 | DL | | D04242J | | 6 | | 275-299 |
| 111Z | | | EK | 0-0 | 78-34-21 | D05712P | | =CC | L | | D04242J | | =CC | M | ALL |
| 201B | 20 | | UB IA | 24-0 | 78-34-21 | D04622P | | 23 | | | D04242J | | 23 | | 050-099, 150-199 |
| 201B | 20 | | UB IA | 23-1 | 78-34-21 | D04622P | | 23 | | | D04242J | | 23 | | 275-299 |
| 201R | 20 | | UB IA | 0-0 | 78-34-21 | D04622P | | 24 | | | D04242J | | 24 | | ALL |
| 202B | 20 | | UB IB | 24-0 | 78-34-21 | D04622P | | 25 | | | D04242J | | 25 | | 050-099, 150-199 |
| 202B | 20 | | UB IB | 23-1 | 78-34-21 | D04622P | | 25 | | | D04242J | | 25 | | 275-299 |
| 202R | 20 | | UB IB | 0-0 | 78-34-21 | D04622P | | 26 | | | D04242J | | 26 | | ALL |
| 205B | 20 | | UB G | 24-0 | SPARE | D04242J | | 32 | | | D04622P | | 32 | | 050-099, 150-199 |
| 205B | 20 | | UB G | 23-1 | SPARE | D04242J | | 32 | | | D04622P | | 32 | | 275-299 |
| 205R | 20 | | UB G | 0-0 | SPARE | D04242J | | 33 | | | D04622P | | 33 | | ALL |
| 206B | 20 | | UB K | 9-0 | 27-81-11 | D02294 | | 2 | | | D05712P | | 4 | | 050-099, 150-199 |
| 206B | 20 | | UB K | 8-6 | 27-81-11 | D02294 | | 2 | | | D05712P | | 4 | | 275-299 |
| 206R | 20 | | UB K | 0-0 | 27-81-11 | D02294 | | 1 | | | D05712P | | 5 | | ALL |
| 303B | 20 | | UC L | 9-0 | 27-81-11 | D02294 | | 3 | | | D05712P | | 6 | | 050-099, 150-199 |
| 303B | 20 | | UC L | 8-6 | 27-81-11 | D02294 | | 3 | | | D05712P | | 6 | | 275-299 |
| 303R | 20 | | UC L | 0-0 | 27-81-11 | D02294 | | 5 | | | D05712P | | 7 | | ALL |
| 303Y | 20 | | UC L | 0-0 | 27-81-11 | D02294 | | 4 | | | D05712P | | 8 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0410

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-----|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W0418 | 286T0418 | | | R WING-R2B-ENG INSTR/ANTI-ICE/SLATS/HYDRAULICS (continued) | | | | | | | | | | | | | | |
| 304B | 20 | VH | MD | 24-0 | 79-32-11 | D04242J | | 15 | | | | | D04622P | | 15 | | | 050-099, 150-199 |
| 304B | 20 | VH | MD | 23-1 | 79-32-11 | D04242J | | 15 | | | | | D04622P | | 15 | | | 275-299 |
| 304R | 20 | VH | MD | 0-0 | 79-32-11 | D04242J | | 13 | | | | | D04622P | | 13 | | | ALL |
| 304Y | 20 | VH | MD | 0-0 | 79-32-11 | D04242J | | 14 | | | | | D04622P | | 14 | | | ALL |
| 304Z | | | MD | 0-0 | 79-32-11 | D04242J | | =CC | M | | | | D04622P | | =CC | M | | ALL |
| 801 | 20 | UA | | 31-0 | SPARE | D05598P | | 12 | | | | | D04380P | | 7 | | | 050-099, 150-199 |
| 801 | 20 | UA | | 30-4 | SPARE | D05598P | | 12 | | | | | D04380P | | 7 | | | 275-299 |
| W0419 | 286T0419 | | | AFDS WRN AND ANN L,P1 TO SHELF | | | | | | | | | | | | | | |
| 001 | 22 | PA | | 25-0 | SPARE | D05553J | | 1 | | | | | D05551J | | 1 | | | ALL |
| 002 | 22 | PA | | 25-0 | SPARE | D05553J | | 2 | | | | | D05551J | | 2 | | | ALL |
| 006 | 24 | PK | | 25-0 | SPARE | D05551J | | 3 | | | | | D05553J | | 3 | | | 150-199 |
| 007 | 24 | PK | | 25-0 | SPARE | D05551J | | 4 | | | | | D05553J | | 4 | | | 150-199 |
| 206B | 22 | PB | IH | 25-0 | 34-12-11 | D05551J | | 7 | | | | | D05553J | | 7 | | | ALL |
| 206R | 22 | PB | IH | 0-0 | 34-12-11 | D05551J | | 6 | | | | | D05553J | | 6 | | | ALL |
| 211 | 20 | UA | | 1-6 | SPARE | D05551J | | | | | | FA | GD00401 | | S.. | 2 | | ALL |
| 211B | 24 | PW | IK | 25-0 | SPARE | D05551J | | 12 | | | | | D05553J | | 12 | | | ALL |
| 211R | 24 | PW | IK | 0-0 | SPARE | D05551J | | 11 | | | | | D05553J | | 11 | | | ALL |
| 211Z | | | IK | 0-0 | SPARE | D05551J | | | | | | FA | D05553J | | 13 | | | ALL |
| FRA | | | | 0-0 | SPARE | D05551J | | | | | | FA | D05551J | | 13 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0410

Page 8 End

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-----------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0420 | 286T0420 | | | L WING-L2A-EEC | | | | | | | | | | | |
| 001 | 20 | | VF | AA | 23-2 | 73-21-11 | D04528P | | 2 | | D04234J | | 7 | | ALL |
| 001Z | | | | AA | 0-0 | 73-21-11 | D04528P | =CC | M | | D04234J | =CC | M | | ALL |
| 013 | 16 | | VF | AM | 23-2 | 73-21-20 | D04234J | | 13 | | D04528P | | 13 | FL | ALL |
| 013Z | | | | AM | 0-0 | 73-21-20 | D04234J | =CC | M | | D04528P | =CC | M | | ALL |
| 017 | 20 | | 98 | O | 8-2 | 28-21-12 | D06116P | | 3 | | D08306P | | 3 | | ALL |
| 017Z | | | | O | 0-0 | 28-21-12 | D06116P | | 2 | | D08306P | | 2 | | ALL |
| 018 | 20 | | 98 | Q | 8-2 | 28-21-12 | D06116P | | 1 | | D08306P | | 6 | | ALL |
| 018Z | | | | Q | 0-0 | 28-21-12 | D06116P | =C1 | | | D08306P | | | FD | ALL |
| 021 | 20 | | VF | AU | 23-2 | 73-21-11 | D04234J | | 8 | | D04528P | | 8 | | ALL |
| 021Z | | | | AU | 0-0 | 73-21-11 | D04234J | =CC | M | | D04528P | =CC | M | | ALL |
| 022 | 16 | | VF | AV | 23-2 | 73-21-11 | D04234J | | 4 | | D04528P | | 6 | FL | ALL |
| 022Z | | | | AV | 0-0 | 73-21-11 | D04234J | =CC | M | | D04528P | =CC | M | | ALL |
| 100 | 20 | | VF | IH | 23-2 | 73-21-19 | D04234J | | 40 | | D04528P | | 40 | | ALL |
| 100Z | | | | IH | 0-0 | 73-21-19 | D04234J | =CC | M | | D04528P | =CC | M | | ALL |
| 103 | 20 | | VF | EC | 23-2 | 73-21-17 | D04528P | | 1 | | D04234J | | 1 | | ALL |
| 103Z | | | | EC | 0-0 | 73-21-17 | D04528P | =CC | M | | D04234J | =CC | M | | ALL |
| 201B | 20 | | HQ | IA | 23-2 | 73-21-13 | D04528P | | 15 | | D04234J | | 15 | | 050-099, 275-299 |
| 201B | 20 | | VG | IA | 23-2 | 73-21-13 | D04528P | | 15 | | D04234J | | 15 | | 150-199 |
| 201R | 20 | | HQ | IA | 0-0 | 73-21-13 | D04528P | | 16 | | D04234J | | 16 | | 050-099, 275-299 |
| 201R | 20 | | VG | IA | 0-0 | 73-21-13 | D04528P | | 16 | | D04234J | | 16 | | 150-199 |
| 201Z | | | | IA | 0-0 | 73-21-13 | D04528P | =CC | M | | D04234J | =CC | M | | ALL |
| 203B | 20 | | VG | S | 23-2 | 73-21-14 | D04234J | | 6 | | D04528P | | 19 | | ALL |
| 203R | 20 | | VG | S | 0-0 | 73-21-14 | D04234J | | 5 | | D04528P | | 20 | | ALL |
| 203Z | | | | S | 0-0 | 73-21-14 | D04234J | =CC | M | | D04528P | =CC | M | | ALL |
| 205B | 20 | | VG | IE | 23-2 | 73-21-14 | D04234J | | 23 | | D04528P | | 23 | | ALL |
| 205R | 20 | | VG | IE | 0-0 | 73-21-14 | D04234J | | 24 | | D04528P | | 24 | | ALL |
| 205Z | | | | IE | 0-0 | 73-21-14 | D04234J | =CC | M | | D04528P | =CC | M | | ALL |
| 206B | 20 | | VG | Y | 23-2 | SPARE | D04234J | CAP | Y | | D04528P | | 30 | | 050-099, 275-276, 278-299 |
| 206B | 20 | | VG | Y | 23-2 | 31-35-14 | D04234J | | 36 | | D04528P | | 30 | | 277 |
| 206R | 20 | | VG | Y | 0-0 | SPARE | D04234J | CAP | Y | | D04528P | | 31 | | 050-099, 275-276, 278-299 |
| 206R | 20 | | VG | Y | 0-0 | 31-35-14 | D04234J | | 35 | | D04528P | | 31 | | 277 |
| 206Z | | | | Y | 0-0 | SPARE | D04234J | DED | | | D04528P | DED | | | 050-099, 275-276, 278-299 |
| 206Z | | | | Y | 0-0 | 31-35-14 | D04234J | =CC | M | | D04528P | =CC | M | | 277 |
| 209B | 20 | | VG | II | 23-2 | 77-12-12 | D04234J | | 3 | | D04528P | | 36 | | ALL |
| 209R | 20 | | VG | II | 0-0 | 77-12-12 | D04234J | | 2 | | D04528P | | 35 | | ALL |
| 209Z | | | | II | 0-0 | 77-12-12 | D04234J | =CC | M | | D04528P | =CC | M | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0420
Page 1
Mar 14/2007



| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0420 | 286T0420 | | | L WING-L2A-EEC (continued) | | | | | | | | | | | |
| 210B | 20 | VG | IJ | | 23-2 | 73-21-17 | D04234J | | 28 | | D04528P | | 9 | | ALL |
| 210R | 20 | VG | IJ | | 0-0 | 73-21-12 | D04234J | | 17 | | D04528P | | 12 | | ALL |
| 210Z | | | IJ | | 0-0 | 73-21-12 | D04234J | =CC | M | | D04528P | =CC | M | | ALL |
| 302B | 20 | HR | MB | | 23-2 | 73-21-13 | D04528P | | 27 | | D04234J | | 27 | | ALL |
| 302R | 20 | HR | MB | | 0-0 | 73-21-13 | D04528P | | 26 | | D04234J | | 26 | | ALL |
| 302Y | 20 | HR | MB | | 0-0 | 73-21-13 | D04528P | | 25 | | D04234J | | 25 | | ALL |
| 302Z | | | MB | | 0-0 | 73-21-13 | D04528P | =CC | M | | D04234J | =CC | M | | ALL |
| 305B | 20 | HR | ME | | 23-2 | 73-21-11 | D04528P | | 4 | | D04234J | | 10 | | ALL |
| 305R | 20 | HR | ME | | 0-0 | 73-21-11 | D04528P | | 5 | | D04234J | | 19 | | ALL |
| 305Y | 20 | HR | ME | | 0-0 | 73-21-11 | D04528P | | 7 | | D04234J | | 9 | | ALL |
| 305Z | | | ME | | 0-0 | 73-21-11 | D04528P | =CC | M | | D04234J | =CC | M | | ALL |
| FRD | | | | | 0-0 | 28-21-12 | D08306P | | 5 | | D08306P | | | FD | ALL |
| FRE | | | | | 0-0 | 28-21-12 | D08306P | | 1 | | D08306P | | | FD | ALL |
| FRF | | | | | 0-0 | 28-21-12 | D08306P | | 7 | | D08306P | | | FD | ALL |
| W0422 | 286T0422 | | | R. WING-R2A-EEC | | | | | | | | | | | |
| 001 | 20 | VF | AA | | 22-11 | 73-21-11 | D04624P | | 2 | | D04244J | | 7 | | ALL |
| 001Z | | | AA | | 0-0 | 73-21-11 | D04624P | =CC | M | | D04244J | =CC | M | | ALL |
| 010 | 20 | VF | AU | | 22-11 | 73-21-11 | D04244J | | 8 | | D04624P | | 8 | | ALL |
| 010Z | | | AU | | 0-0 | 73-21-11 | D04244J | =CC | M | | D04624P | =CC | M | | ALL |
| 012 | 20 | UA | | | 22-11 | SPARE | D04244J | | 35 | | D04624P | | 11 | | 050-099, 150-199 |
| 013 | 16 | VF | AM | | 22-11 | 73-21-20 | D04244J | | 13 | | D04624P | | 13 | FL | ALL |
| 013Z | | | AM | | 0-0 | 73-21-20 | D04244J | =CC | M | | D04624P | =CC | M | | ALL |
| 016 | 20 | VF | X | | 22-11 | SPARE | D04244J | | 18 | | D04624P | | 29 | | ALL |
| 016Z | | | X | | 0-0 | SPARE | D04244J | =CC | M | | D04624P | =CC | M | | ALL |
| 017 | 20 | 98 | O | | 8-4 | 28-21-12 | D06114P | | 3 | | D08308P | | 3 | | ALL |
| 017Z | | | O | | 0-0 | 28-21-12 | D06114P | | 2 | | D08308P | | 2 | | ALL |
| 018 | 20 | 98 | Q | | 8-4 | 28-21-12 | D06114P | | 1 | | D08308P | | 6 | | ALL |
| 018Z | | | Q | | 0-0 | 28-21-12 | D06114P | =C1 | | | D08308P | | | FD | ALL |
| 022 | 16 | VF | AV | | 22-11 | 73-21-11 | D04244J | | 4 | | D04624P | | 6 | FL | ALL |
| 022Z | | | AV | | 0-0 | 73-21-11 | D04244J | =CC | M | | D04624P | =CC | M | | ALL |
| 100 | 20 | VF | IH | | 22-11 | 73-21-19 | D04244J | | 40 | | D04624P | | 40 | | ALL |
| 100Z | | | IH | | 0-0 | 73-21-19 | D04244J | =CC | M | | D04624P | =CC | M | | ALL |
| 103 | 20 | VF | EC | | 22-11 | 73-21-17 | D04624P | | 1 | | D04244J | | 1 | | ALL |
| 103Z | | | EC | | 0-0 | 73-21-17 | D04624P | =CC | M | | D04244J | =CC | M | | ALL |
| 201B | 20 | VG | N | | 22-11 | 73-21-13 | D04244J | | 15 | | D04624P | | 15 | | ALL |
| 201R | 20 | VG | N | | 0-0 | 73-21-13 | D04244J | | 16 | | D04624P | | 16 | | ALL |
| 201Z | | | N | | 0-0 | 73-21-13 | D04244J | =CC | M | | D04624P | =CC | M | | ALL |
| 202B | 20 | VG | R | | 22-11 | 77-12-12 | D04244J | | 2 | | D04624P | | 39 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0420

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0422 | 286T0422 | | | R. WING-R2A-EEC (continued) | | | | | | | | | | | |
| 202R | 20 | VG | R | | 0-0 | 77-12-12 | D04244J | 3 | | | D04624P | 36 | | | ALL |
| 202Z | | | R | | 0-0 | 77-12-12 | D04244J | =CC | M | | D04624P | =CC | M | | ALL |
| 203B | 20 | VG | S | | 22-11 | 73-21-14 | D04244J | 6 | | | D04624P | 19 | | | ALL |
| 203R | 20 | VG | S | | 0-0 | 73-21-14 | D04244J | 5 | | | D04624P | 20 | | | ALL |
| 203Z | | | S | | 0-0 | 73-21-14 | D04244J | =CC | M | | D04624P | =CC | M | | ALL |
| 205B | 20 | VG | IE | | 22-11 | 73-21-14 | D04244J | 23 | | | D04624P | 23 | | | ALL |
| 205R | 20 | VG | IE | | 0-0 | 73-21-14 | D04244J | 24 | | | D04624P | 24 | | | ALL |
| 205Z | | | IE | | 0-0 | 73-21-14 | D04244J | =CC | M | | D04624P | =CC | M | | ALL |
| 206B | 20 | VG | Y | | 22-11 | SPARE | D04244J | CAP | Y | | D04624P | 30 | | | 050-099, 275-276, 278-299 |
| 206B | 20 | VG | Y | | 22-11 | 31-35-15 | D04244J | 36 | | | D04624P | 30 | | | 277 |
| 206R | 20 | VG | Y | | 0-0 | SPARE | D04244J | CAP | Y | | D04624P | 31 | | | 050-099, 275-276, 278-299 |
| 206R | 20 | VG | Y | | 0-0 | 31-35-15 | D04244J | 35 | | | D04624P | 31 | | | 277 |
| 206Z | | | Y | | 0-0 | SPARE | D04244J | DED | | | D04624P | =CC | M | | 050-099, 275-276, 278-299 |
| 206Z | | | Y | | 0-0 | 31-35-15 | D04244J | =CC | M | | D04624P | =CC | M | | 277 |
| 209B | 20 | VG | II | | 22-11 | 73-21-17 | D04244J | 28 | | | D04624P | 10 | | | ALL |
| 209R | 20 | VG | II | | 0-0 | 73-21-12 | D04244J | 17 | | | D04624P | 12 | | | ALL |
| 209Z | | | II | | 0-0 | 73-21-12 | D04244J | =CC | M | | D04624P | =CC | M | | ALL |
| 302B | 20 | VH | P | | 22-11 | 73-21-13 | D04244J | 27 | | | D04624P | 27 | | | ALL |
| 302R | 20 | VH | P | | 0-0 | 73-21-13 | D04244J | 26 | | | D04624P | 26 | | | ALL |
| 302Y | 20 | VH | P | | 0-0 | 73-21-13 | D04244J | 25 | | | D04624P | 25 | | | ALL |
| 302Z | | | P | | 0-0 | 73-21-13 | D04244J | =CC | M | | D04624P | =CC | M | | ALL |
| 305B | 20 | HR | ME | | 22-11 | 73-21-11 | D04624P | 4 | | | D04244J | 10 | | | ALL |
| 305R | 20 | HR | ME | | 0-0 | 73-21-11 | D04624P | 5 | | | D04244J | 19 | | | ALL |
| 305Y | 20 | HR | ME | | 0-0 | 73-21-11 | D04624P | 7 | | | D04244J | 9 | | | ALL |
| 305Z | | | ME | | 0-0 | 73-21-11 | D04624P | =CC | M | | D04244J | =CC | M | | ALL |
| FRD | | | | | 0-0 | 28-21-12 | D08308P | 5 | | | D08308P | | | FD | ALL |
| FRE | | | | | 0-0 | 28-21-12 | D08308P | 1 | | | D08308P | | | FD | ALL |
| FRF | | | | | 0-0 | 28-21-12 | D08308P | 7 | | | D08308P | | | FD | ALL |
| W0424 | 286T0424 | | | L WING FS-S2B-FIRE DETECTION | | | | | | | | | | | |
| 001 | 18 | UA | | | 31-0 | 29-11-11 | D04546P | 5 | | | D04404P | 1 | | | ALL |
| 002 | 18 | UA | | | 31-0 | 29-11-11 | D04546P | 6 | | | D04404P | 2 | | | ALL |
| 451R | 18 | XG | | | 24-0 | 26-11-12 | D04546P | 8 | | | D04218J | 1 | | | ALL |
| 452R | 18 | XG | | | 24-0 | 26-11-11 | D04546P | 2 | | | D04218J | 2 | | | ALL |
| 453R | 18 | XG | | | 24-0 | SPARE | D04546P | 7 | | | D04218J | 3 | | | ALL |
| 454R | 18 | XG | | | 24-0 | 26-11-12 | D04546P | 9 | | | D04218J | 4 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0420
Page 3
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0424 | 286T0424 | | | L WING FS-S2B-FIRE DETECTION (continued) | | | | | | | | | | | | | |
| 455R | 18 | | XG | 24-0 | 26-11-11 | D04546P | | 3 | | | | | D04218J | 5 | | | ALL |
| 456R | 18 | | XG | 24-0 | 26-11-11 | D04546P | | 1 | | | | | D04218J | 6 | | | ALL |
| 457R | 18 | | XG | 24-0 | 26-11-12 | D04546P | | 4 | | | | | D04218J | 7 | | | ALL |
| W0426 | 286T0426 | | | R WING-S2B-FIRE DETECTION | | | | | | | | | | | | | |
| 001 | 18 | | UA | 30-0 | 29-11-21 | D05522P | | 11 | | | | | D04406P | 1 | | | ALL |
| 002 | 18 | | UA | 30-0 | 29-11-21 | D05522P | | 10 | | | | | D04406P | 2 | | | ALL |
| 451R | 18 | | XG | 24-0 | 26-11-22 | D05522P | | 6 | | | | | D04264J | 1 | | | ALL |
| 452R | 18 | | XG | 24-0 | 26-11-21 | D05522P | | 3 | | | | | D04264J | 2 | | | ALL |
| 453R | 18 | | XG | 24-0 | SPARE | D05522P | | 9 | | | | | D04264J | 3 | | | ALL |
| 454R | 18 | | XG | 24-0 | 26-11-22 | D05522P | | 5 | | | | | D04264J | 4 | | | ALL |
| 455R | 18 | | XG | 24-0 | 26-11-21 | D05522P | | 2 | | | | | D04264J | 5 | | | ALL |
| 456R | 18 | | XG | 24-0 | 26-11-21 | D05522P | | 1 | | | | | D04264J | 6 | | | ALL |
| 457R | 18 | | XG | 24-0 | 26-11-22 | D05522P | | 4 | | | | | D04264J | 7 | | | ALL |
| W0428 | 286T0428 | | | P32 TO F4 L FWD GALLEY CONTROL | | | | | | | | | | | | | |
| 001 | 20 | | PA | 7-0 | 33-22-31 | D13446 | | 1 | | | | | SP00244 | | S | | 050-099, 150-199 |
| 002 | 20 | | PA | 4-0 | 33-22-31 | D13446 | | 2 | | | | | GD04194 | A.. | 2 | | 050-099, 150-199 |
| 004 | 24 | | PK | 43-0 | 25-31-12 | D13446 | | 4 | | | | | D08686P | 8 | | | 050-099, 150-199 |
| 005 | 24 | | PK | 43-0 | 25-31-12 | D13446 | | 5 | | | | | D08686P | 5 | | | 050-099, 150-199 |
| 006 | 24 | | PK | 43-0 | 25-31-12 | D13446 | | 6 | | | | | D08686P | 6 | | | 050-099, 150-199 |
| 007 | 24 | | PK | 43-0 | 25-31-12 | D13446 | | 7 | | | | | D08686P | 9 | | | 050-099, 150-199 |
| 009 | 20 | | PA | 4-0 | 25-31-12 | D13446 | | 9 | | | | | GD03932 | D.. | 2 | | 050-099, 150-199 |
| 010 | 16 | | PA | 43-0 | 25-31-12 | D13446 | | 10 | FM | | | | D08686P | 10 | | | 050-099, 150-199 |
| 013 | 20 | | PA | 6-0 | 35-21-12 | D13446 | | 13 | | | | | SP03638 | | S | | 050-099 |
| 013 | 20 | | PA | 7-0 | 35-21-12 | D13446 | | 13 | | | | | SP03638 | | S | | 150-199 |
| 014 | 20 | | PA | 4-0 | 35-21-12 | D13446 | | 14 | | | | | GD03932 | D.. | 2 | | 050-099, 150-199 |
| 015 | 18 | | PA | 43-0 | 30-71-25 | D13446 | | 11 | DK | | | | D08686P | 4 | | | 050-099, 150-199 |
| 016 | 18 | | PA | 4-0 | 30-71-25 | D13446 | | 12 | DK | | | | GD03932 | A.. | 2 | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0420

Page 4 End

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0430 | 286T0430 | | | L WING OUTBD FS-L2-FLIGHT CONTROLS | | | | | | | | | | | | | |
| 001 | 18 | | UA | | 1-7 | 27-88-12 | D04434J | | 21 | | | | SM00001 | | 9 | | ALL |
| 002 | 18 | | UA | | 1-7 | 27-88-12 | D04434J | | 3 | | | | SM00002 | | 9 | | ALL |
| 003 | 18 | | UA | | 1-7 | 27-88-12 | D04434J | | 9 | | | | SM00003 | | 9 | | ALL |
| 004 | 18 | | UA | | 1-7 | 27-88-12 | D04434J | | 1 | | | | SM00004 | | 9 | | ALL |
| 005 | 18 | | UA | | 1-7 | 27-88-12 | D04434J | | 5 | | | | SM00005 | | 9 | | ALL |
| 006 | 18 | | UA | | 1-7 | 27-88-12 | D04434J | | 7 | | | | SM00006 | | 9 | | ALL |
| 007 | 18 | | UA | | 1-7 | 27-88-12 | D04434J | | 11 | | | | SM00007 | | 9 | | ALL |
| 008 | 18 | | UA | | 1-7 | 27-88-12 | D04434J | | 13 | | | | SM00008 | | 9 | | ALL |
| 009 | 18 | | UA | | 1-7 | 27-88-12 | D04434J | | 15 | | | | SM00009 | | 9 | | ALL |
| 010 | 18 | | UA | | 1-7 | 27-88-12 | D04434J | | 17 | | | | SM00010 | | 9 | | ALL |
| 01TB | 20 | | ZZ | L | 8-3 | 27-88-12 | SM00001 | | | 9 | | | SP00118 | | 9 | | ALL |
| 01TI | | | | L | 0-0 | 27-88-12 | SM00001 | | | 9 | | | SP00120 | DED | | | ALL |
| 01TO | | | | L | 0-0 | 27-88-12 | GD03514 | | S.. | N | *1 | | GD03668 | S.. | N | | ALL |
| 01TR | 20 | | ZZ | L | 0-0 | 27-88-12 | D04434J | | | 22 | | | SP00120 | | 9 | | ALL |
| 02TB | 20 | | ZZ | M | 4-3 | 27-88-12 | SM00002 | | | 9 | | | SP00122 | | 9 | | ALL |
| 02TI | | | | M | 0-0 | 27-88-12 | SM00002 | | | 9 | | | SP00124 | DED | | | ALL |
| 02TO | | | | M | 0-0 | 27-88-12 | GD03514 | | S.. | N | *1 | | GD03666 | S.. | N | | ALL |
| 02TR | 20 | | ZZ | M | 0-0 | 27-88-12 | D04434J | | | 4 | | | SP00124 | | 9 | | ALL |
| 03TB | 20 | | ZZ | P | 21-0 | 27-88-12 | SM00003 | | | 9 | | | SP00130 | | 9 | | ALL |
| 03TI | | | | P | 0-0 | 27-88-12 | SM00003 | | | 9 | | | SP00132 | DED | | | ALL |
| 03TO | | | | P | 0-0 | 27-88-12 | GD03514 | | S.. | N | *1 | | GD03672 | S.. | N | | ALL |
| 03TR | 20 | | ZZ | P | 0-0 | 27-88-12 | D04434J | | | 10 | | | SP00132 | | 9 | | ALL |
| 04TB | 20 | | ZZ | A | 16-11 | 27-88-12 | SM00004 | | | 9 | | | SP00134 | | 9 | | ALL |
| 04TI | | | | A | 0-0 | 27-88-12 | SM00004 | | | 9 | | | SP00136 | DED | | | ALL |
| 04TO | | | | A | 0-0 | 27-88-12 | GD03514 | | S.. | N | *1 | | GD03670 | S.. | N | | ALL |
| 04TR | 20 | | ZZ | A | 0-0 | 27-88-12 | D04434J | | | 2 | | | SP00136 | | 9 | | ALL |
| 05TB | 20 | | ZZ | C | 34-3 | 27-88-12 | SM00005 | | | 9 | | | SP00142 | | 9 | | ALL |
| 05TI | | | | C | 0-0 | 27-88-12 | SM00005 | | | 9 | | | SP00144 | DED | | | ALL |
| 05TO | | | | C | 0-0 | 27-88-12 | GD03514 | | S.. | N | *2 | | GD03676 | S.. | N | | ALL |
| 05TR | 20 | | ZZ | C | 0-0 | 27-88-12 | D04434J | | | 6 | | | SP00144 | | 9 | | ALL |
| 06TB | 20 | | ZZ | D | 30-4 | 27-88-12 | SM00006 | | | 9 | | | SP00146 | | 9 | | ALL |
| 06TI | | | | D | 0-0 | 27-88-12 | SM00006 | | | 9 | | | SP00148 | DED | | | ALL |
| 06TO | | | | D | 0-0 | 27-88-12 | GD03514 | | S.. | N | *2 | | GD03674 | S.. | N | | ALL |
| 06TR | 20 | | ZZ | D | 0-0 | 27-88-12 | D04434J | | | 8 | | | SP00148 | | 9 | | ALL |
| 07TB | 20 | | ZZ | F | 47-4 | 27-88-12 | SM00007 | | | 9 | | | SP00154 | | 9 | | ALL |
| 07TI | | | | F | 0-0 | 27-88-12 | SM00007 | | | 9 | | | SP00156 | DED | | | ALL |
| 07TO | | | | F | 0-0 | 27-88-12 | GD03514 | | S.. | N | *2 | | GD03680 | S.. | N | | ALL |
| 07TR | 20 | | ZZ | F | 0-0 | 27-88-12 | D04434J | | | 12 | | | SP00156 | | 9 | | ALL |
| 08TB | 20 | | ZZ | G | 42-10 | 27-88-12 | SM00008 | | | 9 | | | SP00158 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0430

Page 1

Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0430 | 286T0430 | | | L WING OUTBD FS-L2-FLIGHT CONTROLS (continued) | | | | | | | | | | | | | |
| 08TI | | | | G | 0-0 | 27-88-12 | SM00008 | | | 9 | | | SP00160 | DED | | | ALL |
| 08TO | | | | G | 0-0 | 27-88-12 | GD03514 | | S.. | N | *3 | | GD03678 | S.. | N | | ALL |
| 08TR | 20 | 2Z | | G | 0-0 | 27-88-12 | D04434J | | | 14 | | | SP00160 | | 9 | | ALL |
| 09TB | 20 | 2Z | | H | 60-11 | 27-88-12 | SM00009 | | | 9 | | | SP00106 | | 9 | | ALL |
| 09TI | | | | H | 0-0 | 27-88-12 | SM00009 | | | 9 | | | SP00108 | DED | | | ALL |
| 09TO | | | | H | 0-0 | 27-88-12 | GD03514 | | S.. | N | *3 | | GD03684 | S.. | N | | ALL |
| 09TR | 20 | 2Z | | H | 0-0 | 27-88-12 | D04434J | | | 16 | | | SP00108 | | 9 | | ALL |
| 10TB | 20 | 2Z | | J | 55-11 | 27-88-12 | SM00010 | | | 9 | | | SP00110 | | 9 | | ALL |
| 10TI | | | | J | 0-0 | 27-88-12 | SM00010 | | | 9 | | | SP00112 | DED | | | ALL |
| 10TO | | | | J | 0-0 | 27-88-12 | GD03514 | | S.. | N | *3 | | GD03682 | S.. | N | | ALL |
| 10TR | 20 | 2Z | | J | 0-0 | 27-88-12 | D04434J | | | 18 | | | SP00112 | | 9 | | ALL |
| 216B | 18 | UB | | B | 65-0 | 27-89-11 | D04434J | | | 20 | | | D07546J | | 2 | | ALL |
| 216R | 18 | UB | | B | 0-0 | 27-89-11 | D04434J | | | 19 | | | D07546J | | 1 | | ALL |
| A-A | | | | S | 0-0 | 27-88-12 | S00276 | | | BLU | | | SP00106 | | 9 | | ALL |
| A-B | | | | S | 0-0 | 27-88-12 | S00276 | | | RED | | | SP00108 | | 9 | | ALL |
| A-C | | | | T | 0-0 | 27-88-12 | S00282 | | | BLU | | | SP00110 | | 9 | | ALL |
| A-D | | | | T | 0-0 | 27-88-12 | S00282 | | | RED | | | SP00112 | | 9 | | ALL |
| A-G | | | | V | 0-0 | 27-88-12 | S00280 | | | BLU | | | SP00118 | | 9 | | ALL |
| A-H | | | | V | 0-0 | 27-88-12 | S00280 | | | RED | | | SP00120 | | 9 | | ALL |
| A-J | | | | W | 0-0 | 27-88-12 | S00286 | | | BLU | | | SP00122 | | 9 | | ALL |
| A-K | | | | W | 0-0 | 27-88-12 | S00286 | | | RED | | | SP00124 | | 9 | | ALL |
| A-N | | | | Y | 0-0 | 27-88-12 | S00279 | | | BLU | | | SP00130 | | 9 | | ALL |
| A-P | | | | Y | 0-0 | 27-88-12 | S00279 | | | RED | | | SP00132 | | 9 | | ALL |
| A-Q | | | | Z | 0-0 | 27-88-12 | S00285 | | | BLU | | | SP00134 | | 9 | | ALL |
| A-R | | | | Z | 0-0 | 27-88-12 | S00285 | | | RED | | | SP00136 | | 9 | | ALL |
| A-U | | | | AB | 0-0 | 27-88-12 | S00278 | | | BLU | | | SP00142 | | 9 | | ALL |
| A-V | | | | AB | 0-0 | 27-88-12 | S00278 | | | RED | | | SP00144 | | 9 | | ALL |
| A-W | | | | AC | 0-0 | 27-88-12 | S00284 | | | BLU | | | SP00146 | | 9 | | ALL |
| A-X | | | | AC | 0-0 | 27-88-12 | S00284 | | | RED | | | SP00148 | | 9 | | ALL |
| B-A | | | | AE | 0-0 | 27-88-12 | S00277 | | | BLU | | | SP00154 | | 9 | | ALL |
| B-B | | | | AE | 0-0 | 27-88-12 | S00277 | | | RED | | | SP00156 | | 9 | | ALL |
| B-C | | | | AF | 0-0 | 27-88-12 | S00283 | | | BLU | | | SP00158 | | 9 | | ALL |
| B-D | | | | AF | 0-0 | 27-88-12 | S00283 | | | RED | | | SP00160 | | 9 | | ALL |
| W0431 | 286T0431 | | | UPPER LEFT AOA SENSOR TO SHELF-L | | | | | | | | | | | | | |
| 008 | 22 | PA | | | 7-0 | 30-32-11 | D00117 | | | 10 | | | SP02312 | | 9 | | ALL |
| 009 | 20 | PA | | | 9-0 | 30-32-11 | D00117 | | | 9 | | | GD00521 | A.. | 2 | | ALL |
| 010 | 22 | PA | | | 7-0 | 30-32-11 | D00117 | | | 8 | | | SP02310 | | 9 | | ALL |
| 012 | 20 | PA | | | 9-0 | 34-12-11 | D00117 | | | 12 | | | GD00521 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0430

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0431 | 286T0431 | | | UPPER LEFT AOA SENSOR TO SHELF-L (continued) | | | | | | | | | | | | |
| 201B | 22 | PB | IA | | 1-6 | 34-12-11 | D00117 | | 2 | | | SM00001 | | 9 | | ALL |
| 201R | 22 | PB | IA | | 0-0 | 34-12-11 | D00117 | | 1 | | | SM00002 | | 9 | | ALL |
| 202B | 22 | PB | IB | | 1-6 | 34-12-11 | D00121 | | 2 | | | SM00001 | | 9 | | ALL |
| 202R | 22 | PB | IB | | 0-0 | 34-12-11 | D00121 | | 1 | | | SM00002 | | 9 | | ALL |
| 203B | 22 | PB | IC | | 18-0 | 34-12-11 | SM00001 | | | 9 | | D04309J | 5 | | | ALL |
| 203R | 22 | PB | IC | | 0-0 | 34-12-11 | SM00002 | | | 9 | | D04309J | 4 | | | ALL |
| 301B | 24 | PM | MA | | 19-0 | 34-12-11 | D00117 | | 4 | | | D04309J | 2 | | | ALL |
| 301R | 24 | PM | MA | | 0-0 | 34-12-11 | D00117 | | 3 | | | D04309J | 1 | | | ALL |
| 301Y | 24 | PM | MA | | 0-0 | 34-12-11 | D00117 | | 5 | | | D04309J | 3 | | | ALL |
| 302B | 24 | PM | MB | | 19-0 | 34-12-11 | D00121 | | 4 | | | D04309J | 7 | | | ALL |
| 302R | 24 | PM | MB | | 0-0 | 34-12-11 | D00121 | | 3 | | | D04309J | 6 | | | ALL |
| 302Y | 24 | PM | MB | | 0-0 | 34-12-11 | D00121 | | 5 | | | D04309J | 8 | | | ALL |
| W0436 | 286T0436 | | | L WING INBD FS-L2-TURNOFF & LANDING LTS | | | | | | | | | | | | |
| 005 | 18 | UA | | | 2-2 | 27-81-31 | D02298 | | 6 | | | GD03224 | S.. | N | | ALL |
| 201B | 20 | UB | A | | 10-6 | 27-81-31 | D02298 | | 1 | | | D04532P | 1 | | | ALL |
| 201R | 20 | UB | A | | 0-0 | 27-81-31 | D02298 | | 2 | | | D04532P | 2 | | | ALL |
| 301B | 20 | UC | B | | 10-6 | 27-81-31 | D02298 | | 5 | | | D04532P | 3 | | | ALL |
| 301R | 20 | UC | B | | 0-0 | 27-81-31 | D02298 | | 3 | | | D04532P | 4 | | | ALL |
| 301Y | 20 | UC | B | | 0-0 | 27-81-31 | D02298 | | 4 | | | D04532P | 5 | | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0440 | 286T0440 | | | L WING-R2-HYDRAULICS/LIGHTING | | | | | | | | | | | | |
| 001 | 20 | | UA | 30-0 | 29-11-12 | D04280P | | | 1 | | D04536P | | | 1 | | ALL |
| 002 | 20 | | UA | 30-0 | 29-11-12 | D04280P | | | 2 | | D04536P | | | 2 | | ALL |
| 006 | 20 | | UA | 30-0 | 29-11-12 | D04280P | | | 4 | | D04536P | | | 4 | | ALL |
| 007 | 20 | | UA | 30-0 | 30-11-11 | D01594 | | | 1 | | D04536P | | | 7 | | ALL |
| 008 | 18 | | UA | 3-0 | 30-11-11 | D01594 | | | 2 | | GD03738 | | D.. | N | | ALL |
| 009 | 20 | | UA | 29-0 | 30-11-11 | D01594 | | | 4 | | D04536P | | | 9 | | ALL |
| 010 | 20 | | UA | 29-0 | 30-11-11 | D01594 | | | 5 | | D04536P | | | 10 | | ALL |
| 011 | 20 | | UA | 32-0 | SPARE | D04438P | | | 2 | | D04536P | | | 11 | | 150-199 |
| 011 | 20 | | UA | 32-0 | 30-11-11 | D04438P | | | 2 | | D04536P | | | 11 | | 275-299 |
| 012 | 20 | | UA | 32-0 | 30-11-11 | D04438P | | | 1 | | D04536P | | | 12 | | ALL |
| 013 | 20 | | UA | 32-0 | SPARE | D04438P | | | 3 | | D04536P | | | 13 | | 150-199 |
| 013 | 20 | | UA | 32-0 | 30-11-11 | D04438P | | | 3 | | D04536P | | | 13 | | 275-299 |
| 015 | 20 | | UA | 32-0 | 33-43-11 | D04438P | | | 4 | | D04536P | | | 15 | | 050-099 |
| 015 | 18 | | UA | 32-0 | 33-43-11 | D04438P | | | 4 | | D04536P | | DL | | | 150-199, 275-299 |
| 016 | 18 | | UA | 32-0 | 33-44-21 | D04438P | | | 6 | | D04536P | | | 16 | | 050-099 |
| 016 | 18 | | UA | 32-0 | 33-44-21 | D04438P | | | 6 | | D04536P | | DL | | | 150-199, 275-299 |
| 017 | 20 | | UA | 32-0 | SPARE | D04438P | | | 7 | | D04536P | | | 17 | | ALL |
| 018 | 20 | | UA | 30-0 | SPARE | D04280P | | | 7 | | D04536P | | | 18 | | 050-099 |
| 019 | 20 | | UA | 14-0 | 27-81-21 | D01514 | | | 2 | | D04536P | | | 20 | | ALL |
| 020 | 18 | | UA | 14-0 | 27-81-21 | D01514 | | | 3 | | D04536P | | | 21 | DL | ALL |
| 021 | 18 | | UA | 14-0 | 27-81-21 | D01514 | | | 5 | | D04536P | | | 22 | DL | ALL |
| 022 | 18 | | UA | 5-0 | 27-81-21 | D01514 | | | 1 | | GD03640 | | D.. | N | | ALL |
| 023 | 18 | | UA | 5-0 | 27-81-21 | D01514 | | | 8 | | GD03660 | | S.. | N | | ALL |
| 024 | 18 | | UA | 3-0 | 27-81-21 | D02296 | | | 6 | | GD03734 | | S.. | N | | ALL |
| 025 | 18 | | UA | 3-0 | 30-11-11 | D01594 | | | 3 | | GD03738 | | D.. | N | | ALL |
| 026 | 18 | | UA | 4-0 | 30-11-11 | D01594 | | | 6 | | GD03736 | | S.. | N | | ALL |
| 201B | 20 | | UB | A | 11-0 | 27-81-21 | D02296 | | 1 | | D04536P | | | 24 | | ALL |
| 201R | 20 | | UB | A | 0-0 | 27-81-21 | D02296 | | 2 | | D04536P | | | 23 | | ALL |
| 202B | 20 | | UB | AB | 30-0 | 29-11-12 | D04280P | | 6 | | D04536P | | | 6 | | ALL |
| 202R | 20 | | UB | AB | 0-0 | 29-11-12 | D04280P | | 5 | | D04536P | | | 5 | | ALL |
| 301B | 20 | | UC | B | 11-0 | 27-81-21 | D02296 | | 5 | | D04536P | | | 26 | | ALL |
| 301R | 20 | | UC | B | 0-0 | 27-81-21 | D02296 | | 3 | | D04536P | | | 25 | | ALL |
| 301Y | 20 | | UC | B | 0-0 | 27-81-21 | D02296 | | 4 | | D04536P | | | 27 | | ALL |
| W0441 | 286T0441 | | | UPPER RIGHT AOA SENSOR TO SHELF-R | | | | | | | | | | | | |
| 008 | 22 | | PA | 12-0 | 30-32-21 | D00123 | | | 10 | | SP00251 | | | 9 | | ALL |
| 009 | 20 | | PA | 7-0 | 30-32-21 | D00123 | | | 9 | | GD00595 | | A.. | 2 | | ALL |
| 010 | 22 | | PA | 12-0 | 30-32-21 | D00123 | | | 8 | | SP00253 | | | 9 | | ALL |
| 012 | 20 | | PA | 7-0 | 34-12-21 | D00123 | | | 12 | | GD00595 | | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0440

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0441 | 286T0441 | | | UPPER RIGHT AOA SENSOR TO SHELF-R (continued) | | | | | | | | | | | |
| 201B | 22 | | PB | IA | 1-6 | 34-12-21 | D00127 | | | | SM00001 | | | 9 | ALL |
| 201R | 22 | | PB | IA | 0-0 | 34-12-21 | D00127 | | | | SM00002 | | | 9 | ALL |
| 202B | 22 | | PB | IB | 1-6 | 34-12-21 | D00123 | | | | SM00001 | | | 9 | ALL |
| 202R | 22 | | PB | IB | 0-0 | 34-12-21 | D00123 | | | | SM00002 | | | 9 | ALL |
| 203B | 22 | | PB | IC | 21-0 | 34-12-21 | SM00001 | | | 9 | D04317J | | | 5 | ALL |
| 203R | 22 | | PB | IC | 0-0 | 34-12-21 | SM00002 | | | 9 | D04317J | | | 4 | ALL |
| 301B | 24 | | PM | MA | 21-0 | 34-12-21 | D00127 | | | | D04317J | | | 2 | ALL |
| 301R | 24 | | PM | MA | 0-0 | 34-12-21 | D00127 | | | | D04317J | | | 1 | ALL |
| 301Y | 24 | | PM | MA | 0-0 | 34-12-21 | D00127 | | | | D04317J | | | 3 | ALL |
| 302B | 24 | | PM | MB | 21-0 | 34-12-21 | D00123 | | | | D04317J | | | 7 | ALL |
| 302R | 24 | | PM | MB | 0-0 | 34-12-21 | D00123 | | | | D04317J | | | 6 | ALL |
| 302Y | 24 | | PM | MB | 0-0 | 34-12-21 | D00123 | | | | D04317J | | | 8 | ALL |
| W0442 | 286T0442 | | | R WING INBD FS-L2-FLIGHT CONTROLS & HYDRAULICS | | | | | | | | | | | |
| 001 | 20 | | UA | | 30-0 | 29-11-22 | D04168P | | | | D05530P | | | 1 | ALL |
| 002 | 20 | | UA | | 30-0 | 29-11-22 | D04168P | | | | D05530P | | | 2 | ALL |
| 004 | 20 | | UA | | 30-0 | 29-11-22 | D04168P | | | | D05530P | | | 5 | ALL |
| 005 | 18 | | UA | | 3-0 | 27-81-31 | GD03230 | | S.. | N | D01528 | | | 6 | ALL |
| 201B | 20 | | UB | A | 31-0 | 27-88-22 | D04378P | | | | D04628P | | | 1 | ALL |
| 201R | 20 | | UB | A | 0-0 | 27-88-22 | D04378P | | | | D04628P | | | 2 | ALL |
| 203B | 20 | | UB | C | 31-0 | 27-88-22 | D04378P | | | | D04628P | | | 5 | ALL |
| 203R | 20 | | UB | C | 0-0 | 27-88-22 | D04378P | | | | D04628P | | | 6 | ALL |
| 204B | 20 | | UB | D | 31-0 | 27-88-22 | D04378P | | | | D04628P | | | 7 | ALL |
| 204R | 20 | | UB | D | 0-0 | 27-88-22 | D04378P | | | | D04628P | | | 8 | ALL |
| 206B | 20 | | UB | F | 31-0 | 27-88-22 | D04378P | | | | D04628P | | | 11 | ALL |
| 206R | 20 | | UB | F | 0-0 | 27-88-22 | D04378P | | | | D04628P | | | 12 | ALL |
| 207B | 20 | | UB | G | 31-0 | 27-88-22 | D04378P | | | | D04628P | | | 13 | ALL |
| 207R | 20 | | UB | G | 0-0 | 27-88-22 | D04378P | | | | D04628P | | | 14 | ALL |
| 208B | 20 | | UB | H | 31-0 | 27-88-22 | D04378P | | | | D04628P | | | 15 | ALL |
| 208R | 20 | | UB | H | 0-0 | 27-88-22 | D04378P | | | | D04628P | | | 16 | ALL |
| 209B | 20 | | UB | J | 31-0 | 27-88-22 | D04378P | | | | D04628P | | | 17 | ALL |
| 209R | 20 | | UB | J | 0-0 | 27-88-22 | D04378P | | | | D04628P | | | 18 | ALL |
| 210B | 20 | | UB | AC | 30-0 | 29-11-22 | D04168P | | | | D05530P | | | 3 | ALL |
| 210R | 20 | | UB | AC | 0-0 | 29-11-22 | D04168P | | | | D05530P | | | 6 | ALL |
| 211B | 20 | | UB | L | 31-0 | 27-88-22 | D04378P | | | | D04628P | | | 21 | ALL |
| 211R | 20 | | UB | L | 0-0 | 27-88-22 | D04378P | | | | D04628P | | | 22 | ALL |
| 212B | 20 | | UB | M | 31-0 | 27-88-22 | D04378P | | | | D04628P | | | 3 | ALL |
| 212R | 20 | | UB | M | 0-0 | 27-88-22 | D04378P | | | | D04628P | | | 4 | ALL |
| 214B | 20 | | UB | P | 31-0 | 27-88-22 | D04378P | | | | D04628P | | | 9 | ALL |

WIRE LIST

D280T132

91-21-11

Section W0440

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|----|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0442 | 286T0442 | | | R WING INBD FS-L2-FLIGHT CONTROLS & HYDRAULICS (continued) | | | | | | | | | | | | |
| 214R | 20 | UB | P | 0-0 | 27-88-22 | D04378P | | 10 | | | | | D04628P | 10 | | ALL |
| 216B | 20 | UB | V | 17-0 | 27-88-22 | SP00270 | | | 9 | | | | D04628P | 19 | | ALL |
| 216R | 20 | UB | V | 0-0 | 27-88-22 | SP00272 | | | 9 | | | | D04628P | 20 | | ALL |
| 217B | 20 | UB | W | 26-0 | 27-88-22 | SP00274 | | | 9 | | | | D04628P | 25 | | ALL |
| 217R | 20 | UB | W | 0-0 | 27-88-22 | SP00276 | | | 9 | | | | D04628P | 26 | | ALL |
| 219B | 20 | UB | AA | 11-0 | 27-81-31 | D04626P | | 1 | | | | | D01528 | 1 | | ALL |
| 219R | 20 | UB | AA | 0-0 | 27-81-31 | D04626P | | 2 | | | | | D01528 | 2 | | ALL |
| 220B | 20 | UB | Y | 31-0 | SPARE | D04378P | | 23 | | | | | D04628P | 27 | | ALL |
| 220R | 20 | UB | Y | 0-0 | SPARE | D04378P | | 24 | | | | | D04628P | 28 | | ALL |
| 221B | 20 | UB | Z | 31-0 | SPARE | D04378P | | 25 | | | | | D04628P | 29 | | ALL |
| 221R | 20 | UB | Z | 0-0 | SPARE | D04378P | | 26 | | | | | D04628P | 30 | | ALL |
| 223B | 18 | UB | B | 30-3 | 27-89-11 | D04378P | | 19 | | | | | D04626P | 11 | DL | ALL |
| 223R | 18 | UB | B | 0-0 | 27-89-11 | D04378P | | 20 | | | | | D04626P | 12 | DL | ALL |
| 301B | 20 | UC | AB | 11-0 | 27-81-31 | D04626P | | 3 | | | | | D01528 | 5 | | ALL |
| 301R | 20 | UC | AB | 0-0 | 27-81-31 | D04626P | | 4 | | | | | D01528 | 3 | | ALL |
| 301Y | 20 | UC | AB | 0-0 | 27-81-31 | D04626P | | 5 | | | | | D01528 | 4 | | ALL |
| A-A | | | S | 0-0 | 27-88-12 | S00299 | | | BLU | | | | SP00270 | | 9 | 050-099, 150-199, 275-278 |
| A-A | | | S | 0-0 | 27-88-22 | S00299 | | | BLU | | | | SP00270 | | 9 | 280-299 |
| A-B | | | S | 0-0 | 27-88-22 | S00299 | | | RED | | | | SP00272 | | 9 | ALL |
| A-C | | | T | 0-0 | 27-88-22 | S00305 | | | BLU | | | | SP00274 | | 9 | ALL |
| A-D | | | T | 0-0 | 27-88-22 | S00305 | | | RED | | | | SP00276 | | 9 | ALL |
| W0443 | 286T0443 | | | CONTROL COLUMN-CAPT | | | | | | | | | | | | |
| WBB | 22 | VE | | 0-0 | 23-51-11 | TB0207G | | 11 | 2 | | | | QD0008 | | GS | ALL |
| WBG | 22 | VE | | 0-0 | 22-11-32 | TB0207F | | C001 | 2 | | | | QD0017 | | GS | ALL |
| WBK | 22 | VE | | 0-0 | 27-41-11 | TB0207F | | A006 | 2 | | | | QD0003 | | GS | ALL |
| WBL | 22 | VE | | 0-0 | 22-11-22 | TB0207F | | C004 | 2 | | | | QD0013 | | GS | ALL |
| WBN | 22 | VE | | 0-0 | 22-11-22 | TB0207F | | A004 | 2 | | | | QD0010 | | GS | ALL |
| WBO | 22 | VE | | 0-0 | 27-41-11 | TB0207F | | C006 | 2 | | | | QD0004 | | GS | ALL |
| WBR | 22 | VE | | 0-0 | 23-51-11 | TB0207F | | C008 | 2 | | | | QD0009 | | GS | ALL |
| WBU | 22 | VE | | 0-0 | 22-11-12 | TB0207F | | A003 | 2 | | | | QD0016 | | GS | ALL |
| WBV | 22 | VE | | 0-0 | 23-51-11 | TB0207G | | 11 | 2 | | | | QD0006 | | GS | ALL |
| WGR | 22 | VE | | 0-0 | 22-11-12 | TB0207F | | A002 | 2 | | | | QD0012 | | GS | ALL |
| WGY | 22 | VE | | 0-0 | 23-51-11 | TB0207F | | A008 | 2 | | | | QD0007 | | GS | ALL |
| WHT | 22 | VE | | 0-0 | 22-11-12 | TB0207F | | C002 | 2 | | | | QD0015 | | GS | ALL |
| WKY | 22 | VE | | 0-0 | 22-11-32 | TB0207F | | A001 | 2 | | | | QD0014 | | GS | ALL |
| WOR | 22 | VE | | 0-0 | 27-41-11 | TB0207F | | A005 | 2 | | | | QD0001 | | GS | ALL |
| WRD | 22 | VE | | 0-0 | 27-41-11 | TB0207F | | A007 | 2 | | | | QD0005 | | GS | ALL |

WIRE LIST

D280T132

91-21-11

Section W0440

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|--------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0443 | 286T0443 | | | CONTROL COLUMN-CAPT (continued) | | | | | | | | | | | |
| WVI | 22 | | VE | 0-0 | 27-41-11 | TB0207F | C005 | 2 | | QD0002 | | GS | | ALL | |
| WYL | 22 | | VE | 0-0 | 22-11-12 | TB0207F | C003 | 2 | | QD0011 | | GS | | ALL | |
| W0444 | 286T0444 | | | L WING REAR SPAR-L1-BST PUMP | | | | | | | | | | | |
| 001 | 18 | | UA | 12-7 | 28-22-11 | D01542 | | 3 | | GD04110 | S.. | N | *1 | 050-099, 155-199, 276-299 | |
| 001 | 18 | | UA | 12-7 | 28-22-11 | D01542 | | 3 | | GD04110 | S.. | N | | 150-154, 275 | |
| 002 | 14 | | UA | 9-4 | 28-22-12 | D02802 | | 3 | | GD04110 | S.. | N | *1 | 050-099, 155-199, 276-299 | |
| 002 | 14 | | UA | 9-4 | 28-22-12 | D02802 | | 3 | | GD04110 | S.. | N | | 150-154, 275 | |
| 006 | 14 | | UA | 13-0 | 28-31-21 | D12188 | | 3 | | GD04072 | S.. | N | | 155-157, 165-199, 277, 280-299 | |
| 006 | 14 | | UA | 13-2 | 28-31-21 | D12188 | | 3 | | GD04072 | S.. | N | | 278 | |
| 300B | 14 | | OC LY | 22-10 | 28-31-21 | D05558P | | 4 | | D12188 | | 6 | | 155-157, 165-199, 277, 280-299 | |
| 300B | 14 | | OC LY | 23-0 | 28-31-21 | D05558P | | 4 | | D12188 | | 6 | | 278 | |
| 300R | 14 | | OC LY | 0-0 | 28-31-21 | D05558P | | 5 | | D12188 | | 4 | | 155-157, 165-199, 277-299 | |
| 300Y | 14 | | OC LY | 0-0 | 28-31-21 | D05558P | | 6 | | D12188 | | 2 | | 155-157, 165-199, 277-299 | |
| 300Z | | | LY | 0-0 | 28-31-21 | GD03994 | | S.. | N | GD04052 | S.. | N | | 155-157, 165-199, 277-299 | |
| 301B | 18 | | VH A | 26-5 | 28-22-11 | D01542 | | 2 | | D04408P | | 1 | | ALL | |
| 301R | 18 | | VH A | 0-0 | 28-22-11 | D01542 | | 4 | | D04408P | | 2 | | ALL | |
| 301Y | 18 | | VH A | 0-0 | 28-22-11 | D01542 | | 6 | | D04408P | | 3 | | ALL | |
| 301Z | | | A | 0-0 | 28-22-11 | GD04048 | | S.. | N | GD03994 | S.. | N | *1 | 050-099, 155-199, 276-299 | |
| 301Z | | | A | 0-0 | 28-22-11 | GD04048 | | S.. | N | GD03994 | S.. | N | | 150-154, 275 | |
| 302B | 14 | | OC B | 22-7 | 28-22-12 | D05558P | | 1 | | D02802 | | 2 | | ALL | |
| 302R | 14 | | OC B | 0-0 | 28-22-12 | D05558P | | 2 | | D02802 | | 4 | | ALL | |
| 302Y | 14 | | OC B | 0-0 | 28-22-12 | D05558P | | 3 | | D02802 | | 6 | | ALL | |
| 302Z | | | B | 0-0 | 28-22-12 | GD03994 | | S.. | N | GD04052 | S.. | N | *1 | 050-099, 155-199, 276-299 | |
| 302Z | | | B | 0-0 | 28-22-12 | GD03994 | | S.. | N | GD04052 | S.. | N | | 150-154, 275 | |
| W0445 | 286T0445 | | | CONTROL COLUMN-FO | | | | | | | | | | | |
| WBB | 22 | | VE | 0-0 | 23-51-21 | TB0307G | | 11 | 2 | QD0025 | | GS | | ALL | |
| WBG | 22 | | VE | 0-0 | 22-11-32 | TB0307F | | C001 | 2 | QD0034 | | GS | | ALL | |
| WBK | 22 | | VE | 0-0 | 27-41-21 | TB0307F | | A006 | 2 | QD0020 | | GS | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0440
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|---------|-------|------|------|--------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0445 | 286T0445 | | | CONTROL COLUMN-FO (continued) | | | | | | | | | | | | |
| WBL | 22 | | VE | 0-0 | 22-11-22 | TB0307F | A004 | 2 | | QD0030 | | GS | | ALL | | |
| WBN | 22 | | VE | 0-0 | 22-11-22 | TB0307F | C004 | 2 | | QD0027 | | GS | | ALL | | |
| WBO | 22 | | VE | 0-0 | 27-41-21 | TB0307F | C006 | 2 | | QD0021 | | GS | | ALL | | |
| WBR | 22 | | VE | 0-0 | 23-51-21 | TB0307F | C008 | 2 | | QD0026 | | GS | | ALL | | |
| WBU | 22 | | VE | 0-0 | 22-11-12 | TB0307F | A003 | 2 | | QD0033 | | GS | | ALL | | |
| WBU | 22 | | VE | 0-0 | 23-51-21 | TB0307G | | 11 | 2 | QD0023 | | GS | | ALL | | |
| WGR | 22 | | VE | 0-0 | 22-11-12 | TB0307F | C003 | 2 | | QD0029 | | GS | | ALL | | |
| WGY | 22 | | VE | 0-0 | 23-51-21 | TB0307F | A008 | 2 | | QD0024 | | GS | | ALL | | |
| WHT | 22 | | VE | 0-0 | 22-11-12 | TB0307F | C002 | 2 | | QD0032 | | GS | | ALL | | |
| WKY | 22 | | VE | 0-0 | 22-11-32 | TB0307F | A001 | 2 | | QD0031 | | GS | | ALL | | |
| WOR | 22 | | VE | 0-0 | 27-41-21 | TB0307F | A005 | 2 | | QD0018 | | GS | | ALL | | |
| WRD | 22 | | VE | 0-0 | 27-41-21 | TB0307F | A007 | 2 | | QD0022 | | GS | | ALL | | |
| WVI | 22 | | VE | 0-0 | 27-41-21 | TB0307F | C005 | 2 | | QD0019 | | GS | | ALL | | |
| WYL | 22 | | VE | 0-0 | 22-11-12 | TB0307F | A002 | 2 | | QD0028 | | GS | | ALL | | |
| W0446 | 286T0446 | | | L WING REAR SPAR-L2A-FUEL/FLT CONT | | | | | | | | | | | | |
| 005 | 18 | | UA | 1-1 | 27-51-41 | D01630 | | 10 | | GD03462 | S.. | N | | ALL | | |
| 018 | 18 | | UA | 1-9 | 28-43-11 | SP00600 | | | 9 | GD03356 | D.. | N | | ALL | | |
| 019 | 20 | | UA | 11-3 | 27-11-11 | D02292 | | 1 | | D05702P | 1 | | | 150-154, 275 | | |
| 020 | 20 | | UA | 11-3 | 27-11-11 | D02292 | | 5 | | D05702P | 2 | | | 150-154, 275 | | |
| 021 | 18 | | UA | 11-1 | 27-11-11 | D02292 | | 3 | DK | GD03938 | S.. | N | | ALL | | |
| 022 | 18 | | VF | Y | 19-9 | 27-62-11 | D02264 | 1 | | D04590P | 14 | | | ALL | | |
| 022Z | | | | Y | 0-0 | 27-62-11 | GD03966 | S.. | N | GD03940 | S.. | N | *2 | ALL | | |
| 023 | 18 | | UA | 2-2 | 27-62-11 | D02264 | | 2 | | GD03360 | D.. | N | | ALL | | |
| 049 | 18 | | UA | 2-5 | 32-42-11 | GD03774 | | S.. | N | D02028 | 3 | | | ALL | | |
| 050 | 18 | | UA | 2-10 | 32-42-11 | GD03774 | | S.. | N | D02032 | 3 | | | ALL | | |
| 051 | 18 | | UA | 2-4 | 32-42-11 | GD03764 | | S.. | N | D02044 | 3 | | | ALL | | |
| 053 | 18 | | UA | 3-0 | 28-41-21 | D01534 | | 10 | | GD03370 | S.. | N | | ALL | | |
| 054 | 18 | | UA | 3-0 | 28-41-21 | D01534 | | 8 | | GD03372 | D.. | N | | ALL | | |
| 058 | 18 | | UA | 1-8 | 27-13-11 | D01574 | | 1 | | GD03374 | D.. | N | | ALL | | |
| 059 | 18 | | UA | 1-8 | 27-13-11 | D01574 | | 9 | | GD03374 | D.. | N | | ALL | | |
| 062 | 18 | | UA | 2-2 | 32-42-11 | V00029 | GND | N | | GD03982 | S.. | N | | ALL | | |
| 063 | 18 | | UA | 2-7 | 32-42-11 | V00031 | GND | N | | GD03982 | S.. | N | | ALL | | |
| 064 | 18 | | UA | 2-1 | 32-42-11 | V00037 | GND | N | | GD03984 | S.. | N | | ALL | | |
| 065 | 20 | | VF | AB | 14-10 | 28-41-21 | D04414P | | 7 | D01534 | 5 | | | ALL | | |
| 065Z | | | | AB | 0-0 | 28-41-21 | D04414P | | | D01534 | | | FB | ALL | | |
| 0RBK | 20 | | 8Z | DD | 24-2 | 28-41-21 | D01582 | | 16 | D04594P | 3 | | | ALL | | |
| 0RBU | 20 | | 8Z | DD | 0-0 | 28-41-21 | D01582 | | 5 | D04594P | 5 | | | ALL | | |
| 0RGR | 20 | | 8Z | DD | 0-0 | 28-41-21 | D01582 | | 2 | D04594P | 4 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0440

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|---------|------|------|---------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0446 | 286T0446 | | | L WING REAR SPAR-L2A-FUEL/FLT CONT (continued) | | | | | | | | | | | |
| 0RVI | 20 | 8Z | DD | | 0-0 | 28-41-21 | D01582 | | 4 | | | D04594P | 7 | | ALL |
| 0RYL | 20 | 8Z | DD | | 0-0 | 28-41-21 | D01582 | | 3 | | | D04594P | 2 | | ALL |
| 0WBK | 20 | 8Z | DD | | 0-0 | 28-41-21 | D01582 | | 7 | | | D04594P | 6 | | ALL |
| 0WBN | 20 | 8Z | DD | | 0-0 | 28-41-21 | D01582 | | 6 | | | D04594P | 8 | | ALL |
| 0WBU | 20 | 8Z | DD | | 0-0 | 28-41-21 | D01582 | | 12 | | | D04594P | 13 | | ALL |
| 0WBY | 20 | 8Z | DD | | 0-0 | 28-41-21 | D01582 | | 13 | | | D04594P | 14 | | ALL |
| 0WGR | 20 | 8Z | DD | | 0-0 | 28-41-21 | D01582 | | 10 | | | D04594P | 12 | | ALL |
| 0WHT | 20 | 8Z | DD | | 0-0 | 28-41-21 | D01582 | | 1 | | | D04594P | 1 | | ALL |
| 0WOR | 20 | 8Z | DD | | 0-0 | 28-41-21 | D01582 | | 8 | | | D04594P | 11 | | ALL |
| 0WRD | 20 | 8Z | DD | | 0-0 | 28-41-21 | D01582 | | 9 | | | D04594P | 9 | | ALL |
| 0WVI | 20 | 8Z | DD | | 0-0 | 28-41-21 | D01582 | | 14 | | | D04594P | 15 | | ALL |
| 0WYL | 20 | 8Z | DD | | 0-0 | 28-41-21 | D01582 | | 11 | | | D04594P | 10 | | ALL |
| 201B | 20 | VG | C | | 25-3 | 27-58-21 | D01578 | | 9 | | | D04590P | 15 | | ALL |
| 201R | 20 | VG | C | | 0-0 | 27-58-21 | D01578 | | 8 | | | D04590P | 16 | | ALL |
| 201Z | | | C | | 0-0 | 27-58-21 | GD03376 | | S.. | N | | GD03940 | S.. | N | *2 050-099, 150-154, 162-165, 275-276 |
| 201Z | | | C | | 0-0 | 27-58-21 | GD03376 | | S.. | N | | GD03940 | S.. | N | *3 155-157, 166-199, 277-299 |
| 202B | 20 | VG | D | | 59-0 | 27-51-41 | D01630 | | 8 | | | D04610P | 1 | | ALL |
| 202R | 20 | VG | D | | 0-0 | 27-51-41 | D01630 | | 9 | | | D04610P | 2 | | ALL |
| 202Z | | | D | | 0-0 | 27-51-41 | GD03462 | | S.. | N | | GD03968 | S.. | N | ALL |
| 209B | 20 | VG | R | | 19-6 | 32-42-11 | D02028 | | 1 | | | D05562P | 5 | | ALL |
| 209R | 20 | VG | R | | 0-0 | 32-42-11 | D02028 | | 2 | | | D05562P | 6 | | ALL |
| 209Z | | | R | | 0-0 | 32-42-11 | GD03774 | | S.. | N | | GD04090 | S.. | N | *2 ALL |
| 210B | 20 | VG | AA | | 19-10 | 32-42-11 | D02032 | | 1 | | | D05562P | 7 | | ALL |
| 210R | 20 | VG | AA | | 0-0 | 32-42-11 | D02032 | | 2 | | | D05562P | 8 | | ALL |
| 210Z | | | AA | | 0-0 | 32-42-11 | GD03774 | | S.. | N | | GD04090 | S.. | N | *2 ALL |
| 211B | 20 | VG | BB | | 24-1 | 32-42-11 | D02044 | | 1 | | | D05562P | 9 | | ALL |
| 211R | 20 | VG | BB | | 0-0 | 32-42-11 | D02044 | | 2 | | | D05562P | 10 | | ALL |
| 211Z | | | BB | | 0-0 | 32-42-11 | GD03764 | | S.. | N | | GD04090 | S.. | N | *1 ALL |
| 212B | 18 | VG | CC | | 19-0 | 28-43-11 | SP00598 | | 9 | | | D04590P | 10 | | ALL |
| 212R | 18 | VG | CC | | 0-0 | 28-43-11 | SP00600 | | 9 | | | D04590P | 11 | | ALL |
| 212Z | | | CC | | 0-0 | 28-43-11 | GD03396 | | S.. | N | | GD03940 | S.. | N | *3 050-099, 150-154, 162-165, 275-276 |
| 212Z | | | CC | | 0-0 | 28-43-11 | GD03396 | | S.. | N | | GD03940 | S.. | N | *4 155-157, 166-199, 277-299 |
| 213B | 20 | VG | Z | | 14-10 | 28-41-21 | D04414P | | 3 | | | D01534 | 4 | | ALL |
| 213R | 20 | VG | Z | | 0-0 | 28-41-21 | D04414P | | 4 | | | D01534 | 3 | | ALL |
| 213Z | | | Z | | 0-0 | 28-41-21 | D04414P | | | | FA | D01534 | | | FB ALL |

WIRE LIST
D280T132

91-21-11
Section W0440
Page 6
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0446 | 286T0446 | | | L WING REAR SPAR-L2A-FUEL/FLT CONT (continued) | | | | | | | | | | | | | |
| 214B | 20 | VG | I | 14-10 | 28-41-21 | D04414P | | 5 | | | | | D01534 | 7 | | | ALL |
| 214R | 20 | VG | I | 0-0 | 28-41-21 | D04414P | | 6 | | | | | D01534 | 6 | | | ALL |
| 214Z | | | I | 0-0 | 28-41-21 | D04414P | | | | | | | D01534 | | FA | | ALL |
| 215B | 20 | VG | IO | 11-3 | 27-11-11 | D02292 | | 1 | | | | | D05702P | 1 | | FB | 050-099, 155-199, 276-299 |
| 215R | 20 | VG | IO | 0-0 | 27-11-11 | D02292 | | 5 | | | | | D05702P | 2 | | | 050-099, 155-199, 276-299 |
| 215Z | | | IO | 0-0 | 27-11-11 | D02292 | | | DED | | | | D05702P | DED | | | 050-099, 155-199, 276-299 |
| 216B | 20 | VG | IP | 36-3 | 27-18-11 | D01586 | | 1 | | | | | D04590P | 20 | | | 155-157, 166-199, 277-299 |
| 216R | 20 | VG | IP | 0-0 | 27-18-11 | D01586 | | 2 | | | | | D04590P | 4 | | | 155-157, 166-199, 277-299 |
| 216Z | | | IP | 0-0 | 27-18-11 | GD04006 | | S.. | N | | | | GD03940 | S.. | N | *1 | 155-157, 166-199, 277-299 |
| 217B | 20 | VG | IQ | 87-1 | 27-18-11 | D01638 | | 2 | | | | | D04590P | 7 | | | 155-157, 166-199, 277-299 |
| 217R | 20 | VG | IQ | 0-0 | 27-18-11 | D01638 | | 1 | | | | | D04590P | 22 | | | 155-157, 166-199, 277-299 |
| 217Z | | | IQ | 0-0 | 27-18-11 | GD03952 | | S.. | N | | | | GD03940 | S.. | N | *1 | 155-157, 166-199, 277-299 |
| 301B | 20 | VH | J | 25-3 | 27-58-21 | D01578 | | 12 | | | | | D04590P | 17 | | | ALL |
| 301R | 20 | VH | J | 0-0 | 27-58-21 | D01578 | | 10 | | | | | D04590P | 18 | | | ALL |
| 301Y | 20 | VH | J | 0-0 | 27-58-21 | D01578 | | 11 | | | | | D04590P | 19 | | | ALL |
| 301Z | | | J | 0-0 | 27-58-21 | GD03376 | | S.. | N | | | | GD03940 | S.. | N | *2 | 050-099, 150-154, 162-165, 275-276 |
| 301Z | | | J | 0-0 | 27-58-21 | GD03376 | | S.. | N | | | | GD03940 | S.. | N | *3 | 155-157, 166-199, 277-299 |
| 302B | 20 | VH | S | 26-6 | 27-13-11 | D01574 | | 3 | | | | | D04414P | 9 | | | ALL |
| 302R | 20 | VH | S | 0-0 | 27-13-11 | D01574 | | 2 | | | | | D04414P | 8 | | | ALL |
| 302Y | 20 | VH | S | 0-0 | 27-13-11 | D01574 | | 10 | | | | | D04414P | 10 | | | ALL |
| 302Z | | | S | 0-0 | 27-13-11 | GD04002 | | S.. | N | | | | GD04090 | S.. | N | *1 | ALL |
| 303 | 20 | UA | | 1-7 | 31-31-25 | D04590P | | | | | | | GD03968 | S.. | N | | 050-099, 150-154, 162-165, 275-276 |
| 303 | 20 | UA | | 1-7 | 31-31-25 | D04590P | | | | | | | GD03968 | S.. | N | *1 | 155-157, 166-199, 277-299 |
| 303B | 18 | VH | MC | 19-0 | 31-31-25 | D04590P | | 13 | | | | | SP03692 | 9 | | | ALL |
| 303R | 18 | VH | MC | 0-0 | 31-31-25 | D04590P | | 9 | | | | | SP03690 | 9 | | | ALL |
| 303Y | 18 | VH | MC | 0-0 | 31-31-25 | D04590P | | 12 | | | | | SP03690 | 9 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0440

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0446 | 286T0446 | | | L WING REAR SPAR-L2A-FUEL/FLT CONT (continued) | | | | | | | | | | | |
| 303Z | | | | MC | 0-0 | 31-31-25 | D04590P | | | FC | SP03690 | REF | | FD | ALL |
| 304B | 20 | VH | | MD | 36-6 | 27-18-11 | D01586 | 4 | | | D04594P | 17 | | | 155-157, 166-199, 277-299 |
| 304R | 20 | VH | | MD | 0-0 | 27-18-11 | D01586 | 3 | | | D04594P | 18 | | | 155-157, 166-199, 277-299 |
| 304Y | 20 | VH | | MD | 0-0 | 27-18-11 | D01586 | 5 | | | D04594P | 16 | | | 155-157, 166-199, 277-299 |
| 304Z | | | | MD | 0-0 | 27-18-11 | GD04006 | S.. | N | | GD03968 | S.. | N | | 155-157, 166-199, 277-299 |
| 305B | 20 | VH | | ME | 89-4 | 27-18-11 | D01638 | 4 | | | SP02644 | 9 | | | 155-157, 166-199, 277-299 |
| 305R | 20 | VH | | ME | 0-0 | 27-18-11 | D01638 | 3 | | | SP05088 | 9 | | | 155-157, 166-199, 277-299 |
| 305Y | 20 | VH | | ME | 0-0 | 27-18-11 | D01638 | 5 | | | SP02640 | 9 | | | 155-157, 166-199, 277-299 |
| 305Z | | | | ME | 0-0 | 27-18-11 | GD03952 | S.. | N | | GD03940 | S.. | N | *2 | 155-157, 166-199, 277-299 |
| 401B | 20 | U4 | | K | 59-0 | 27-51-41 | D01630 | 4 | | | D04610P | 3 | | | ALL |
| 401G | 20 | U4 | | K | 0-0 | 27-51-41 | D01630 | 7 | | | D04610P | 6 | | | ALL |
| 401R | 20 | U4 | | K | 0-0 | 27-51-41 | D01630 | 5 | | | D04610P | 4 | | | ALL |
| 401Y | 20 | U4 | | K | 0-0 | 27-51-41 | D01630 | 6 | | | D04610P | 5 | | | ALL |
| 401Z | | | | K | 0-0 | 27-51-41 | GD03462 | S.. | N | | GD03968 | S.. | N | | 050-099, 150-154, 162-165, 275-276 |
| 401Z | | | | K | 0-0 | 27-51-41 | GD03462 | S.. | N | | GD03968 | S.. | N | *1 | 155-157, 166-199, 277-299 |
| 405B | 20 | U4 | | V | 36-3 | 27-18-11 | D01586 | 2 | | | D04590P | 4 | | | 050-099, 150-154, 162-165, 275-276 |
| 405G | 20 | U4 | | V | 0-0 | 27-18-11 | D01586 | 4 | | | D04590P | 6 | | | 050-099, 150-154, 162-165, 275-276 |
| 405R | 20 | U4 | | V | 0-0 | 27-18-11 | D01586 | 1 | | | D04590P | 20 | | | 050-099, 150-154, 162-165, 275-276 |
| 405Y | 20 | U4 | | V | 0-0 | 27-18-11 | D01586 | 5 | | | D04590P | 5 | | | 050-099, 150-154, 162-165, 275-276 |
| 405Z | | | | V | 0-0 | 27-18-11 | GD04006 | S.. | N | | GD03940 | S.. | N | *4 | 050-099, 150-154, 162-165, 275-276 |
| 406B | 20 | U4 | | W | 87-8 | 27-18-11 | D01638 | 2 | | | D04590P | 7 | | | 050-099, 150-154, 162-165, 275-276 |
| 406G | 20 | U4 | | W | 0-0 | 27-18-11 | D01638 | 1 | | | D04590P | 22 | | | 050-099, 150-154, 162-165, 275-276 |

WIRE LIST
D280T132

91-21-11
Section W0440
Page 8
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0446 | 286T0446 | | | L WING REAR SPAR-L2A-FUEL/FLT CONT (continued) | | | | | | | | | | | | | |
| 406R | 20 | U4 | W | 0-0 | 27-18-11 | D01638 | | 5 | | | | | SP02640 | | 9 | | 050-099, 150-154, 162-165, 275-276 |
| 406Y | 20 | U4 | W | 0-0 | 27-18-11 | D01638 | | 4 | | | | | SP02644 | | 9 | | 050-099, 150-154, 162-165, 275-276 |
| 406Z | | | W | 0-0 | 27-18-11 | GD03952 | | S.. | N | | | | GD03940 | S.. | N | *4 | 050-099, 150-154, 162-165, 275-276 |
| 407B | 20 | U4 | X | 58-10 | 27-58-11 | D01630 | | 2 | | | | | D04590P | | 2 | | ALL |
| 407G | 20 | U4 | X | 0-0 | 27-58-11 | D01630 | | 1 | | | | | D04590P | | 1 | | ALL |
| 407R | 20 | U4 | X | 0-0 | 27-58-11 | D01630 | | 11 | | | | | D04590P | | 3 | | ALL |
| 407Y | 20 | U4 | X | 0-0 | 27-58-11 | D01630 | | 3 | | | | | D04590P | | 23 | | ALL |
| 407Z | | | X | 0-0 | 27-58-11 | GD03462 | | S.. | N | | | | GD03940 | S.. | N | *3 | 050-099, 150-154, 162-165, 275-276 |
| 407Z | | | X | 0-0 | 27-58-11 | GD03462 | | S.. | N | | | | GD03940 | S.. | N | *4 | 155-157, 166-199, 277-299 |
| 42T1 | | | EE | 0-0 | 28-41-21 | D01552 | | =C1 | | | | | D05562P | | =C1 | | ALL |
| 42TO | | | EE | 0-0 | 28-41-21 | GD04148 | | S.. | N | | | | GD04090 | S.. | N | | ALL |
| 42TX | | 8X | EE | 23-6 | 28-41-21 | D01552 | | 1 | | | | | D05562P | | 1 | | 050-099, 150-199, 275-278 |
| 42TX | 20 | 8X | EE | 23-6 | 28-41-21 | D01552 | | 1 | | | | | D05562P | | 1 | | 280-299 |
| A-A | | | A | 0-0 | 28-43-11 | TS0168 | | RED | | | | | SP00598 | | 9 | | ALL |
| A-B | | | A | 0-0 | 28-43-11 | TS0168 | | RED | | | | | SP00600 | | 9 | | ALL |
| A-C | | | | 0-0 | 27-18-11 | M01150 | | A | | | | | SP02640 | | 9 | | ALL |
| A-D | | | | 0-0 | 27-18-11 | M01151 | | A | | | | | SP02644 | | 9 | | ALL |
| A-E | | | | 0-0 | 31-31-25 | TS0168 | | WHT | | | | | SP03690 | | 9 | | 050-099 |
| A-E | | | B | 0-0 | 31-31-25 | TS0168 | | WHT | | | | | SP03690 | | 9 | | 150-199, 275-299 |
| A-F | | | | 0-0 | 31-31-25 | TS0168 | | WHT | | | | | SP03692 | | 9 | | 050-099 |
| A-F | | | B | 0-0 | 31-31-25 | TS0168 | | WHT | | | | | SP03692 | | 9 | | 150-199, 275-299 |
| FRA | | | | 0-0 | 28-41-21 | D04414P | | | | | FA | | GD04090 | S.. | N | | ALL |
| FRB | | | | 0-0 | 28-41-21 | D01534 | | | | | FB | | GD04088 | S.. | N | | ALL |
| FRC | | | | 0-0 | 31-31-25 | D04590P | | | | | FC | | D04590P | | 8 | | ALL |
| FRD | | | | 0-0 | 31-31-25 | SP03690 | | REF | | | FD | | GD03396 | S.. | N | | 050-099 |
| FRD | | | | 0-6 | 31-31-25 | SP03690 | | REF | | | FD | | GD03396 | S.. | N | | 150-199, 275-299 |
| WHTZ | | | DD | 0-0 | 28-41-21 | GD04148 | | S.. | N | | | | GD03968 | S.. | N | | ALL |
| W0448 | 286T0448 | | | RIGHT WING REAR SPAR-R2A-FUEL/FLT CONT | | | | | | | | | | | | | |
| 017 | 18 | UA | | 1-10 | 28-41-23 | GD03334 | | D.. | N | | | | D02820 | | 8 | | ALL |
| 018 | 18 | UA | | 1-9 | 28-41-23 | GD03336 | | S.. | N | | | | D02820 | | 10 | | ALL |
| 020 | 18 | UA | | 2-6 | 28-41-22 | GD03338 | | D.. | N | | | | D01536 | | 8 | | ALL |
| 021 | 18 | UA | | 2-5 | 28-41-22 | GD03420 | | S.. | N | | | | D01536 | | 10 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0440

Page 9

Mar 07/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|---------|-------|------|------|--------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0448 | 286T0448 | | | RIGHT WING REAR SPAR-R2A-FUEL/FLT CONT (continued) | | | | | | | | | | | |
| 023 | 18 | UA | | | 2-2 | 32-42-11 | GD03776 | S.. | N | | D02036 | 3 | | | ALL |
| 024 | 18 | UA | | | 2-5 | 32-42-11 | GD03776 | S.. | N | | D02040 | 3 | | | ALL |
| 025 | 18 | UA | | | 2-0 | 32-42-11 | GD03782 | S.. | N | | D02048 | 3 | | | ALL |
| 035 | 18 | UA | | | 1-6 | 27-13-11 | GD03346 | D.. | N | | D02286 | 1 | | | ALL |
| 036 | 18 | UA | | | 1-6 | 27-13-11 | GD03346 | D.. | N | | D02286 | 9 | | | ALL |
| 045 | 18 | UA | | | 2-4 | 32-42-11 | V00033 | GND | N | | GD03986 | S.. | N | | ALL |
| 046 | 18 | UA | | | 2-6 | 32-42-11 | V00035 | GND | N | | GD03986 | S.. | N | | ALL |
| 047 | 18 | UA | | | 1-11 | 32-42-11 | V00039 | GND | N | | GD03988 | S.. | N | | ALL |
| 048 | 20 | VF | AD | | 14-10 | 28-41-22 | D04418P | | 10 | | D01536 | 5 | | | ALL |
| 048Z | | | AD | | 0-0 | 28-41-22 | D04418P | | | FA | D01536 | | | FB | ALL |
| 049 | 20 | VF | AG | | 15-3 | 28-41-23 | D04418P | | 5 | | D02820 | 5 | | | ALL |
| 049Z | | | AG | | 0-0 | 28-41-23 | D04418P | | | FC | D02820 | | | FD | ALL |
| 0BLK | 20 | 8Y | S | | 15-3 | 28-41-23 | D05880P | | 4 | | D02818 | 3 | | | ALL |
| 0BLU | 20 | 8Y | S | | 0-0 | 28-41-23 | D05880P | | 7 | | D02818 | 5 | | | ALL |
| 0GRN | 20 | 8Y | S | | 0-0 | 28-41-23 | D05880P | | 3 | | D02818 | 2 | | | ALL |
| 0RBK | 20 | 8Z | R | | 24-5 | 28-41-22 | D04268P | | 3 | | D01584 | 16 | | | ALL |
| 0RBU | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 5 | | D01584 | 5 | | | ALL |
| 0RED | 20 | 8Y | S | | 0-0 | 28-41-23 | D05880P | | 5 | | D02818 | 4 | | | ALL |
| 0RGR | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 4 | | D01584 | 2 | | | ALL |
| 0RVI | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 7 | | D01584 | 4 | | | ALL |
| 0RYL | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 2 | | D01584 | 3 | | | ALL |
| 0WBK | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 6 | | D01584 | 7 | | | ALL |
| 0WBN | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 8 | | D01584 | 6 | | | ALL |
| 0WBU | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 13 | | D01584 | 12 | | | ALL |
| 0WBY | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 14 | | D01584 | 13 | | | ALL |
| 0WGR | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 12 | | D01584 | 10 | | | ALL |
| 0WHT | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 1 | | D01584 | 1 | | | ALL |
| 0WOR | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 11 | | D01584 | 8 | | | ALL |
| 0WRD | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 9 | | D01584 | 9 | | | ALL |
| 0WVI | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 15 | | D01584 | 14 | | | ALL |
| 0WYL | 20 | 8Z | R | | 0-0 | 28-41-22 | D04268P | | 10 | | D01584 | 11 | | | ALL |
| 0YEL | 20 | 8Y | S | | 0-0 | 28-41-23 | D05880P | | 2 | | D02818 | 1 | | | ALL |
| 201B | 20 | VG | M | | 19-11 | 32-42-11 | D04538P | | 5 | | D02036 | 1 | | | ALL |
| 201R | 20 | VG | M | | 0-0 | 32-42-11 | D04538P | | 8 | | D02036 | 2 | | | ALL |
| 201Z | | | M | | 0-0 | 32-42-11 | GD04098 | S.. | N | | GD03776 | S.. | N | | ALL |
| 202B | 20 | VG | N | | 20-2 | 32-42-11 | D04538P | | 6 | | D02040 | 1 | | | ALL |
| 202R | 20 | VG | N | | 0-0 | 32-42-11 | D04538P | | 9 | | D02040 | 2 | | | ALL |
| 202Z | | | N | | 0-0 | 32-42-11 | GD04098 | S.. | N | | GD03776 | S.. | N | | ALL |
| 203B | 20 | VG | P | | 24-5 | 32-42-11 | D04538P | | 7 | | D02048 | 1 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0440

Page 10

Mar 07/2008



| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|--|----------|-------|---------|-------|------|------|---------|-------|-------------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0448 | 286T0448 | | | RIGHT WING REAR SPAR-R2A-FUEL/FLT CONT (continued) | | | | | | | | | | | |
| 203R | 20 | VG | P | 0-0 | 32-42-11 | | D04538P | 10 | | | D02048 | 2 | | | ALL |
| 203Z | | | P | 0-0 | 32-42-11 | | GD04098 | S.. | N | | GD03782 | S.. | N | | ALL |
| 204B | 20 | VG | AB | 14-10 | 28-41-22 | | D04418P | 11 | | | D01536 | 4 | | | ALL |
| 204R | 20 | VG | AB | 0-0 | 28-41-22 | | D04418P | 12 | | | D01536 | 3 | | | ALL |
| 204Z | | | AB | 0-0 | 28-41-22 | | D04418P | | | FA | D01536 | | | FB | ALL |
| 205B | 20 | VG | AC | 14-10 | 28-41-22 | | D04418P | 6 | | | D01536 | 7 | | | ALL |
| 205R | 20 | VG | AC | 0-0 | 28-41-22 | | D04418P | 7 | | | D01536 | 6 | | | ALL |
| 205Z | | | AC | 0-0 | 28-41-22 | | D04418P | | | FA | D01536 | | | FB | ALL |
| 206B | 20 | VG | AE | 15-3 | 28-41-23 | | D04418P | 13 | | | D02820 | 4 | | | ALL |
| 206R | 20 | VG | AE | 0-0 | 28-41-23 | | D04418P | 14 | | | D02820 | 3 | | | ALL |
| 206Z | | | AE | 0-0 | 28-41-23 | | D04418P | | | FC | D02820 | | | FD | ALL |
| 207B | 20 | VG | AF | 15-3 | 28-41-23 | | D04418P | 1 | | | D02820 | 7 | | | ALL |
| 207R | 20 | VG | AF | 0-0 | 28-41-23 | | D04418P | 2 | | | D02820 | 6 | | | ALL |
| 207Z | | | AF | 0-0 | 28-41-23 | | D04418P | | | FC | D02820 | | | FD | ALL |
| 22TI | | | V | 0-0 | 28-41-22 | | D04538P | =C1 | | | D01560 | =C1 | | | ALL |
| 22TO | | | V | 0-0 | 28-41-22 | | GD04098 | S.. | N | | GD04156 | S.. | N | | ALL |
| 22TX | | 8X | V | 23-9 | 28-41-22 | | D04538P | 1 | | | D01560 | 1 | | | ALL |
| 301B | 20 | VH | G | 26-9 | 27-13-11 | | D02286 | 3 | | | D05514P | 13 | | | ALL |
| 301R | 20 | VH | G | 0-0 | 27-13-11 | | D02286 | 2 | | | D05514P | 12 | | | ALL |
| 301Y | 20 | VH | G | 0-0 | 27-13-11 | | D02286 | 10 | | | D05514P | 14 | | | ALL |
| 301Z | | | G | 0-0 | 27-13-11 | | GD04000 | S.. | N | | GD03946 | S.. | N | | ALL |
| 38TI | | | T | 0-0 | 28-41-23 | | D06080P | =C1 | | | D02814 | =C1 | | | ALL |
| 38TO | | | T | 0-0 | 28-41-23 | | GD03946 | S.. | N | | GD04142 | S.. | N | | ALL |
| 38TX | | 8X | T | 14-9 | 28-41-23 | | D06080P | 1 | | | D02814 | 1 | | | ALL |
| BLKZ | | | S | 0-0 | 28-41-23 | | GD04140 | S.. | N | | GD04142 | S.. | N | | ALL |
| FRA | | | | 0-0 | 28-41-22 | | D04418P | | | FA | GD04140 | S.. | N | | ALL |
| FRB | | | | 0-0 | 28-41-22 | | D01536 | | | FB | GD04094 | S.. | N | | ALL |
| FRC | | | | 0-0 | 28-41-23 | | D04418P | | | FC | GD04140 | S.. | N | | ALL |
| FRD | | | | 0-0 | 28-41-23 | | D02820 | | | FD | GD03336 | S.. | N | | ALL |
| WHTZ | | | R | 0-0 | 28-41-22 | | GD03946 | S.. | N | | GD04156 | S.. | N | | ALL |
| W0449 | 286T0449 | | | P3 TO WARNING ELECTRONICS UNIT AND AURAL WARN SPEAKER | | | | | | | | | | | |
| 003 | 24 | PK | | 20-0 | 31-51-21 | | D04321J | 4 | | | D04303P | 9 | | | ALL |
| 004 | 24 | PK | | 9-0 | 31-51-12 | | D00699 | 4 | | | SP00039 | 9 | | | ALL |
| 005 | 20 | PA | | 1-8 | 31-51-32 | | D04303P | 10 | | | GD00301 | S.. | 2 | | ALL |
| 201B | 24 | PW | IA | 20-0 | SPARE | | D04321J | 2 | | | D04303P | 5 | | | ALL |
| 201R | 24 | PW | IA | 0-0 | SPARE | | D04321J | 1 | | | D04303P | 4 | | | ALL |
| 201Z | | | IA | 0-0 | SPARE | | D04321J | 3 | | | D04303P | 6 | | | ALL |
| 302 | 20 | UA | | 1-6 | 31-51-32 | | D04303P | | | MB | GD00301 | S.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0440

Page 11

Mar 07/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|------------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | |
| W0449 | 286T0449 | | | P3 TO WARNING ELECTRONICS UNIT AND AURAL WARN SPEAKER (continued) | | | | | | | | | | |
| 302 | 20 | | UA | | 1-8 | 31-51-32 | D04303P | | | MB | GD00301 | S.. | 2 | 150-199, 275-299 |
| 302B | 24 | | PX | MB | 28-0 | 31-51-32 | D00699 | | 5 | | D04303P | | 12 | ALL |
| 302R | 24 | | PX | MB | 0-0 | 31-51-32 | D00699 | | 3 | | D04303P | | 11 | ALL |
| 302Y | 24 | | PX | MB | 0-0 | 31-51-32 | D00699 | | 6 | | D04303P | | | MB ALL |
| 302Z | | | | MB | 0-0 | 31-51-32 | D00699 | | DED | | D04303P | | | MB ALL |

WIRE LIST
D280T132

91-21-11
Section W0440
Page 12 End
Mar 07/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0450 | 286T0450 | | | L WING REAR SPAR-L2B-ANTI SKID/FUEL | | | | | | | | | | | | |
| 007 | 20 | VF | B | 18-9 | 28-42-31 | D01530 | | 1 | | | D04598P | 9 | | | 050-099, 155-199, 276-299 | |
| 007 | 20 | VF | B | 19-4 | 28-42-31 | D01530 | | 1 | | | D04598P | 9 | | | 150-154, 275 | |
| 007Z | | | B | 0-0 | 28-42-31 | GD04124 | | S.. | N | | GD03992 | S.. | N | | 050-099, 150-154, 162-165, 275-276 | |
| 007Z | | | B | 0-0 | 28-42-31 | GD03520 | | S.. | N | | GD03992 | S.. | N | | 155-157, 166-199, 277-299 | |
| 008 | 18 | UA | | 3-0 | 28-42-11 | D01530 | | 2 | DK | | GD03378 | D.. | N | | ALL | |
| 009 | 20 | VF | G | 18-9 | 28-42-11 | D01530 | | 3 | | | D04598P | 8 | | | 050-099, 155-199, 276-299 | |
| 009 | 20 | VF | G | 19-4 | 28-42-11 | D01530 | | 3 | | | D04598P | 8 | | | 150-154, 275 | |
| 009Z | | | G | 0-0 | 28-42-11 | GD04124 | | S.. | N | | GD03992 | S.. | N | | 050-099, 150-154, 162-165, 275-276 | |
| 009Z | | | G | 0-0 | 28-42-11 | GD03520 | | S.. | N | | GD03992 | S.. | N | | 155-157, 166-199, 277-299 | |
| 010 | 18 | UA | | 3-3 | 28-42-11 | D01530 | | 4 | DK | | GD03364 | S.. | N | | 050-099, 155-199, 276-299 | |
| 010 | 18 | UA | | 2-11 | 28-42-11 | D01530 | | 4 | DK | | GD03364 | S.. | N | | 150-154, 275 | |
| 020 | 18 | UA | | 2-6 | 32-42-11 | GD03770 | | S.. | N | | D02030 | 3 | | | ALL | |
| 021 | 18 | UA | | 2-11 | 32-42-11 | GD03770 | | S.. | N | | D02034 | 3 | | | ALL | |
| 022 | 18 | UA | | 2-9 | 32-42-11 | GD03764 | | S.. | N | | D02046 | 3 | | | 050-099, 155-199, 276-299 | |
| 022 | 18 | UA | | 2-5 | 32-42-11 | GD03764 | | S.. | N | | D02046 | 3 | | | 150-154, 275 | |
| 023 | 18 | UA | | 2-5 | 32-42-11 | V00030 | | GND | N | | GD03982 | S.. | N | | 050-099, 155-199, 276-299 | |
| 023 | 18 | UA | | 2-6 | 32-42-11 | V00030 | | GND | N | | GD03982 | S.. | N | | 150-154, 275 | |
| 024 | 18 | UA | | 2-9 | 32-42-11 | V00032 | | GND | N | | GD03982 | S.. | N | | 050-099, 155-199, 276-299 | |
| 024 | 18 | UA | | 2-11 | 32-42-11 | V00032 | | GND | N | | GD03982 | S.. | N | | 150-154, 275 | |
| 025 | 18 | UA | | 2-6 | 32-42-11 | V00038 | | GND | N | | GD03984 | S.. | N | | 050-099, 155-199, 276-299 | |
| 025 | 18 | UA | | 2-2 | 32-42-11 | V00038 | | GND | N | | GD03984 | S.. | N | | 150-154, 275 | |
| 026 | 18 | UA | | 3-3 | 28-31-11 | GD03388 | | D.. | N | | D12180 | 4 | | | 050-099, 155-199, 276-299 | |
| 027 | 18 | UA | | 3-2 | 28-31-11 | GD04070 | | S.. | N | | D12180 | 7 | | | 050-099, 155-199, 276-299 | |
| 028 | 18 | UA | | 3-0 | 28-31-12 | GD05818 | | D.. | N | | D12184 | 4 | | | 050-099, 155-199, 276-299 | |

WIRE LIST

D280T132

91-21-11

Section W0450

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0450 | 286T0450 | | | L WING REAR SPAR-L2B-ANTI SKID/FUEL (continued) | | | | | | | | | | | | |
| 029 | 18 | | UA | 3-0 | 28-31-12 | GD05814 | S.. | N | | D12184 | 7 | | | 050-099, 155-199, 276-299 | | |
| 030 | 18 | | UA | 3-0 | 28-42-13 | GD03366 | D.. | N | | D12192 | 2 | DK | | 155-157, 165-199, 277-299 | | |
| 031 | 18 | | UA | 3-0 | 28-42-13 | GD03448 | S.. | N | | D12192 | 4 | DK | | 155-157, 165-199, 277-299 | | |
| 100 | 20 | | VF | DY | 15-3 | 28-42-13 | | | 7 | D12192 | 3 | | | 155-157, 165-199, 277-299 | | |
| 100Z | | | | DY | 0-0 | 28-42-13 | | S.. | N | GD04110 | | S.. | N | 155-157, 165-199, 277-299 | | |
| 201B | 18 | | VG | A | 28-0 | 25-65-11 | | | 3 | D04598P | 15 | | | 050-099, 155-199, 276-299 | | |
| 201B | 18 | | VG | A | 28-2 | 25-65-11 | | | 3 | D04598P | 15 | | | 150-154, 275 | | |
| 201R | 18 | | VG | A | 0-0 | 25-65-11 | | | 4 | D04598P | 16 | | | ALL | | |
| 201Z | | | | A | 0-0 | 25-65-11 | | S.. | N | GD03992 | | S.. | N | ALL | | |
| 202B | 20 | | VG | C | 23-0 | 32-42-11 | | | 1 | D04598P | 2 | | | 050-099, 155-199, 276-299 | | |
| 202B | 20 | | VG | C | 22-11 | 32-42-11 | | | 1 | D04598P | 2 | | | 150-154, 275 | | |
| 202R | 20 | | VG | C | 0-0 | 32-42-11 | | | 2 | D04598P | 3 | | | ALL | | |
| 202Z | | | | C | 0-0 | 32-42-11 | | S.. | N | GD03956 | | S.. | N | ALL | | |
| 203B | 20 | | VG | D | 23-5 | 32-42-11 | | | 1 | D04598P | 4 | | | 050-099, 155-199, 276-299 | | |
| 203B | 20 | | VG | D | 23-4 | 32-42-11 | | | 1 | D04598P | 4 | | | 150-154, 275 | | |
| 203R | 20 | | VG | D | 0-0 | 32-42-11 | | | 2 | D04598P | 5 | | | ALL | | |
| 203Z | | | | D | 0-0 | 32-42-11 | | S.. | N | GD03956 | | S.. | N | ALL | | |
| 204B | 20 | | VG | E | 27-8 | 32-42-11 | | | 1 | D04598P | 6 | | | 050-099, 155-199, 276-299 | | |
| 204B | 20 | | VG | E | 27-6 | 32-42-11 | | | 1 | D04598P | 6 | | | 150-154, 275 | | |
| 204R | 20 | | VG | E | 0-0 | 32-42-11 | | | 2 | D04598P | 7 | | | ALL | | |
| 204Z | | | | E | 0-0 | 32-42-11 | | S.. | N | GD03956 | | S.. | N | ALL | | |
| 300B | 20 | | VH | LY | 70-0 | 28-31-12 | | | 4 | D12184 | 5 | | | 050-099, 155-199, 276-299 | | |
| 300R | 20 | | VH | LY | 0-0 | 28-31-12 | | | 5 | D12184 | 2 | | | 050-099, 155-199, 276-299 | | |
| 300Y | 20 | | VH | LY | 0-0 | 28-31-12 | | | 6 | D12184 | 3 | | | 050-099, 155-199, 276-299 | | |
| 300Z | | | | LY | 0-0 | 28-31-12 | | S.. | N | GD05814 | | S.. | N | 050-099, 155-199, 276-299 | | |
| 301B | 20 | | VH | F | 31-3 | 29-31-11 | | | 1 | D04598P | 10 | | | ALL | | |

WIRE LIST
D280T132

91-21-11
Section W0450
Page 2
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0450 | 286T0450 | | | L WING REAR SPAR-L2B-ANTI SKID/FUEL (continued) | | | | | | | | | | | | |
| 301R | 20 | VH | F | 0-0 | 29-31-11 | D00034 | | 2 | | | | D04598P | 11 | | ALL | |
| 301Y | 20 | VH | F | 0-0 | 29-31-11 | D00034 | | 3 | | | | D04598P | 12 | | ALL | |
| 301Z | | | F | 0-0 | 29-31-11 | GD04086 | | | S.. | N | | GD03992 | S.. | N | ALL | |
| 302B | 20 | VH | MB | 13-6 | 28-31-11 | D08374P | | 2 | | | | D12180 | 5 | | 050-099, 155-199, 276-299 | |
| 302R | 20 | VH | MB | 0-0 | 28-31-11 | D08374P | | 3 | | | | D12180 | 2 | | 050-099, 155-199, 276-299 | |
| 302Y | 20 | VH | MB | 0-0 | 28-31-11 | D08374P | | 1 | | | | D12180 | 3 | | 050-099, 155-199, 276-299 | |
| 302Z | | | MB | 0-0 | 28-31-11 | GD04050 | | | S.. | N | *3 | GD04056 | S.. | N | 050-099, 155-199, 276-299 | |
| W0451 | 286T0451 | | | CAUTION & WARNING L.,PANEL TO SHELVES | | | | | | | | | | | | |
| 001 | 24 | PK | | 27-0 | 22-14-11 | D04323J | | 1 | | | | D04347P | 14 | | ALL | |
| 002 | 24 | PK | | 27-0 | SPARE | D04323J | | 2 | | | | D04347P | 12 | | ALL | |
| 003 | 24 | PK | | 29-0 | 31-51-21 | D05525J | | 6 | | | | D04347P | 6 | | ALL | |
| 004 | 24 | PK | | 22-0 | 31-51-33 | D05203J | | 15 | | | | D04347P | 15 | | ALL | |
| 005 | 24 | PK | | 22-0 | 31-51-41 | D05203J | | 38 | | | | D04347P | 9 | | ALL | |
| 006 | 24 | PK | | 12-0 | 31-51-21 | SP00505 | | | | S | | D04347P | 10 | | 050-099, 155-199, 276-299 | |
| 006 | 24 | PK | | 22-0 | 31-51-21 | D05203J | | 10 | | | | D04347P | 10 | | 150-154, 275 | |
| 007 | 24 | PK | | 22-0 | 31-51-31 | D05203J | | 8 | | | | D04347P | 7 | | ALL | |
| 008 | 24 | PK | | 12-0 | 31-51-21 | SP00503 | | | | S | | D04347P | 11 | | 050-099, 155-199, 276-299 | |
| 008 | 24 | PK | | 22-0 | 31-51-21 | D05203J | | 11 | | | | D04347P | 11 | | 150-154, 275 | |
| 009 | 24 | PK | | 27-0 | 31-51-42 | D04323J | | 6 | | | | D04347P | 24 | | ALL | |
| 010 | 24 | PK | | 22-0 | 31-51-41 | D05203J | | 1 | | | | D04347P | 1 | | ALL | |
| 011 | 24 | PK | | 22-0 | 31-51-41 | D05203J | | 2 | | | | D04347P | 2 | | ALL | |
| 012 | 24 | PK | | 22-0 | 31-51-41 | D05203J | | 3 | | | | D04347P | 3 | | ALL | |
| 013 | 24 | PK | | 22-0 | 31-51-41 | D05203J | | 4 | | | | D04347P | 4 | | ALL | |
| 014 | 24 | PK | | 22-0 | 31-51-42 | D05203J | | 5 | | | | D04347P | 5 | | ALL | |
| 015 | 24 | PK | | 22-0 | 34-16-11 | D05203J | | 6 | | | | D04347P | 16 | | ALL | |
| 016 | 24 | PK | | 22-0 | 31-41-16 | D05203J | | 7 | | | | D04347P | 8 | | ALL | |
| 017 | 24 | PK | | 29-0 | 27-32-11 | D05525J | | 1 | | | | D04347P | 26 | | ALL | |
| 018 | 24 | PK | | 13-0 | 31-51-42 | D04347P | | 13 | | | | D05209P | 12 | | ALL | |
| 019 | 24 | PK | | 22-0 | 34-16-11 | D05203J | | 39 | | | | D04347P | 19 | | ALL | |
| 020 | 24 | PK | | 27-0 | 31-51-21 | D04323J | | 11 | | | | D04347P | 21 | | ALL | |
| 021 | 24 | PV | AU | 20-0 | 34-61-13 | D05203J | | 21 | | | | D05209P | 1 | | ALL | |
| 021Z | | | AU | 0-0 | 34-61-13 | D05203J | | DED | | | | D05209P | DED | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0450

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0451 | 286T0451 | | | CAUTION & WARNING L., PANEL TO SHELVES (continued) | | | | | | | | | | | |
| 022 | 24 | PV | AV | | 20-0 | 34-61-13 | D05203J | | 22 | | D05209P | | 2 | | ALL |
| 022Z | | | AV | | 0-0 | 34-61-13 | D05203J | | DED | | D05209P | | DED | | ALL |
| 023 | 24 | PV | AW | | 20-0 | 34-61-13 | D05203J | | 23 | | D05209P | | 3 | | ALL |
| 023Z | | | AW | | 0-0 | 34-61-13 | D05203J | | DED | | D05209P | | DED | | ALL |
| 024 | 24 | PV | AX | | 20-0 | 34-61-13 | D05203J | | 24 | | D05209P | | 4 | | ALL |
| 024Z | | | AX | | 0-0 | 34-61-13 | D05203J | | DED | | D05209P | | DED | | ALL |
| 025 | 24 | PV | AY | | 20-0 | 34-61-13 | D05203J | | 25 | | D05209P | | 5 | | ALL |
| 025Z | | | AY | | 0-0 | 34-61-13 | D05203J | | DED | | D05209P | | DED | | ALL |
| 026 | 24 | PK | | | 20-0 | 34-61-13 | D05203J | | 26 | | D05209P | | 6 | | ALL |
| 027 | 24 | PK | | | 20-0 | 34-61-13 | D05203J | | 27 | | D05209P | | 7 | | ALL |
| 028 | 24 | PK | | | 20-0 | 34-61-13 | D05203J | | 28 | | D05209P | | 8 | | ALL |
| 029 | 24 | PK | | | 20-0 | 34-61-13 | D05203J | | 29 | | D05209P | | 9 | | ALL |
| 030 | 24 | PK | | | 20-0 | 34-61-13 | D05203J | | 30 | | D05209P | | 10 | | ALL |
| 031 | 24 | PK | | | 20-0 | 34-61-13 | D05203J | | 31 | | D05209P | | 11 | | ALL |
| 032 | 24 | PK | | | 29-0 | 31-51-21 | D04347P | | 30 | | D05525J | | 2 | | ALL |
| 033 | 24 | PK | | | 27-0 | SPARE | D04347P | | 31 | | D04323J | | 3 | | ALL |
| 034 | 24 | PK | | | 13-0 | SPARE | D04347P | | 29 | | D05209P | | 13 | | ALL |
| 035 | 24 | PK | | | 29-0 | 21-61-51 | D04347P | | 25 | | D05525J | | 16 | | 050-099, 275-299 |
| 035 | 24 | PK | | | 29-0 | 21-61-51 | D04347P | | 25 | | D05525J | | 3 | | 150-199 |
| 036 | 24 | PK | | | 20-0 | SPARE | D05203J | | 16 | | D05209P | | 16 | | ALL |
| 037 | 24 | PK | | | 20-0 | SPARE | D05203J | | 17 | | D05209P | | 17 | | ALL |
| 038 | 24 | PK | | | 13-0 | 31-51-42 | D05209P | | 20 | | D04347P | | 20 | | ALL |
| 039 | 22 | PA | | | 22-0 | SPARE | D05203J | | 12 | | D04347P | | 28 | | ALL |
| 041 | 20 | PA | | | 27-0 | 27-32-31 | D04323J | | 8 | | D04347P | | 42 | | ALL |
| 042 | 24 | PK | | | 13-0 | SPARE | D05209P | | 15 | | D04347P | | 43 | | ALL |
| 043 | 24 | PK | | | 27-0 | SPARE | D04323J | | 7 | | D04347P | | 44 | | ALL |
| 044 | 24 | PK | | | 13-0 | SPARE | D05209P | | 14 | | D04347P | | 45 | | ALL |
| 045 | 24 | PK | | | 29-0 | 34-16-11 | D05525J | | 3 | | D04347P | | 32 | | 275-299 |
| 046 | 24 | PK | | | 29-0 | SPARE | D05525J | | 4 | | D04347P | | 33 | | 050-099 |
| 046 | 24 | PK | | | 29-0 | 34-16-11 | D05525J | | 4 | | D04347P | | 33 | | 275-299 |
| 047 | 24 | PK | | | 22-0 | 31-51-43 | D05203J | | 40 | | D04347P | | 46 | | ALL |
| 048 | 24 | PK | | | 20-0 | 31-31-21 | D05209P | | 18 | | D05203J | | 18 | | ALL |
| 049 | 24 | PK | | | 20-0 | 31-31-21 | D05209P | | 19 | | D05203J | | 19 | | ALL |
| 050 | 24 | PK | | | 23-0 | 31-31-22 | SP00223 | | | 9 | D05203J | | 37 | | ALL |
| 054 | 22 | PA | | | 27-0 | 34-45-13 | D05209P | | 24 | | D04323J | | 4 | | 050-099, 150-152 |
| 054 | 22 | PA | | | 25-0 | 34-45-13 | D05209P | | 22 | | D04323J | | 4 | | 153-154 |
| 054 | 22 | PA | | | 25-0 | 34-45-13 | D05209P | | 24 | | D04323J | | 4 | | 155-156, 162-166 |
| 055 | 22 | PA | | | 27-0 | SPARE | D04347P | | 38 | | D04323J | | 5 | | 153-154 |
| 057 | 22 | PA | | | 29-0 | 21-66-11 | D04347P | | 56 | | D05525J | | 17 | | 050-099, 162-199 |

WIRE LIST
D280T132

91-21-11
Section W0450
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|---------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0451 | 286T0451 | | | CAUTION & WARNING L.,PANEL TO SHELVES (continued) | | | | | | | | | | | | |
| 058 | 22 | | PA | | 29-0 | 21-66-11 | D04347P | | 57 | | | | D05525J | 18 | | 050-099, 162-199 |
| 059 | 22 | | PA | | 29-0 | 21-66-11 | D04347P | | 58 | | | | D05525J | 19 | | 050-099, 162-199 |
| 060 | 22 | | PA | | 29-0 | 21-66-41 | D04347P | | 59 | | | | D05525J | 20 | | 050-099, 150, 152-199 |
| 061 | 22 | | PA | | 29-0 | 21-66-21 | D04347P | | 60 | | | | D05525J | 21 | | 050-099, 162-199 |
| 110 | 20 | | PA | | 29-0 | 38-32-11 | D04347P | | 27 | | | | D05525J | 5 | | 050-099, 150-199, 277-299 |
| 110 | 20 | | PA | | 29-0 | SPARE | D04347P | | 27 | | | | D05525J | 5 | | 276 |
| 201B | 24 | | PW | IA | 29-0 | 34-46-11 | D05525J | | 8 | | | | D04347P | 23 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-46-11 | D05525J | | 7 | | | | D04347P | 22 | | ALL |
| 201Z | | | | IA | 0-0 | 34-46-11 | D05525J | | 9 | | | | D04347P | DED | | ALL |
| 202B | 24 | | PW | IB | 27-0 | SPARE | D04323J | | 10 | | | | D04347P | 50 | | 050-099 |
| 202R | 24 | | PW | IB | 0-0 | SPARE | D04323J | | 9 | | | | D04347P | 49 | | 050-099 |
| 202Z | | | | IB | 0-0 | SPARE | D04323J | | 12 | | | | D04347P | 52 | | 050-099 |
| 203 | 20 | | UA | | 3-0 | 31-51-33 | GD00301 | S.. | 2 | | | | D04347P | | IC | ALL |
| 203B | 24 | | PW | IC | 22-0 | 31-51-33 | D05203J | | 33 | | | | D04347P | 18 | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 31-51-33 | D05203J | | 32 | | | | D04347P | 17 | | ALL |
| 203Z | | | | IC | 0-0 | 31-51-33 | D05203J | | 34 | | | | D04347P | | IC | ALL |
| 204 | 20 | | UA | | 3-0 | 27-32-11 | D04347P | | | | ID | GD00301 | S.. | 2 | | ALL |
| 204B | 24 | | PW | ID | 29-0 | 27-32-11 | D05525J | | 11 | | | | D04347P | 37 | | ALL |
| 204R | 24 | | PW | ID | 0-0 | 27-32-11 | D05525J | | 10 | | | | D04347P | 36 | | ALL |
| 204Z | | | | ID | 0-0 | 27-32-11 | D05525J | | 12 | | | | D04347P | | ID | ALL |
| 205 | 20 | | UA | | 3-0 | 27-32-11 | D04347P | | | | IE | GD00301 | S.. | 2 | | ALL |
| 205B | 24 | | PW | IE | 29-0 | 27-32-11 | D05525J | | 14 | | | | D04347P | 40 | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 27-32-11 | D05525J | | 13 | | | | D04347P | 39 | | ALL |
| 205Z | | | | IE | 0-0 | 27-32-11 | D05525J | | 15 | | | | D04347P | | IE | ALL |
| 207 | 20 | | UA | | 4-0 | 27-32-11 | D04347P | | | | IG | GD00727 | S.. | 2 | | ALL |
| 207B | 24 | | PW | IG | 27-0 | 27-32-11 | D04347P | | 48 | | | | D04323J | 14 | | ALL |
| 207R | 24 | | PW | IG | 0-0 | 27-32-11 | D04347P | | 47 | | | | D04323J | 13 | | ALL |
| 207Z | | | | IG | 0-0 | 27-32-11 | D04347P | | | | IG | D04323J | 15 | | ALL | |
| 209B | 24 | | PL | II | 4-0 | 31-51-31 | D04347P | | 55 | | | | GD00727 | S.. | 2 | 050-099, 155-156, 162-166 |
| 209R | 24 | | PL | II | 0-0 | 31-51-31 | D04347P | | 54 | | | | GD00727 | S.. | 2 | 050-099, 155-156, 162-166 |
| 902B | 24 | | PW | AA | 0-0 | 34-53-11 | D05203J | | 14 | | | | D04323J | 10 | | 275-299 |
| 902R | 24 | | PW | AA | 10-0 | 34-53-11 | D05203J | | 13 | | | | D04323J | 9 | | 275-299 |
| 902Z | | | | AA | 0-0 | 34-53-11 | D05203J | | 9 | | | | D04323J | 12 | | 275 |
| 902Z | | | | AA | 0-0 | 34-53-11 | D05203J | | 11 | | | | D04323J | 12 | | 276-299 |

WIRE LIST

D280T132

91-21-11

Section W0450

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0452 | 286T0452 | | | R WING REAR SPAR -R2B- ANTI-SKID/FUEL | | | | | | | | | | | |
| 008 | 18 | | UA | | 2-6 | 28-42-11 | GD03470 | D.. | N | | D01532 | 2 | DK | | ALL |
| 009 | 20 | | VF | F | 17-0 | 28-42-11 | D04278P | 18 | | | D01532 | 3 | | | ALL |
| 009Z | | | | F | 0-0 | 28-42-11 | GD04044 | S.. | N | | GD04120 | S.. | N | | ALL |
| 010 | 18 | | UA | | 2-7 | 28-42-11 | GD03344 | S.. | N | | D01532 | 4 | DK | | ALL |
| 019 | 18 | | UA | | 2-0 | 32-42-11 | GD04100 | S.. | N | | D02038 | 3 | | | 050-099 |
| 019 | 18 | | 5A | | 2-0 | 32-42-11 | GD04100 | S.. | N | | D02038 | 3 | | | 150-199, 275-299 |
| 020 | 18 | | UA | | 2-4 | 32-42-11 | GD04100 | S.. | N | | D02042 | 3 | | | 050-099 |
| 020 | 18 | | 5A | | 2-4 | 32-42-11 | GD04100 | S.. | N | | D02042 | 3 | | | 150-199, 275-299 |
| 021 | 18 | | UA | | 2-6 | 32-42-11 | GD03782 | S.. | N | | D02050 | 3 | | | 050-099 |
| 021 | 18 | | 5A | | 2-6 | 32-42-11 | GD03782 | S.. | N | | D02050 | 3 | | | 150-199, 275-299 |
| 024 | 18 | | UA | | 2-0 | 32-42-11 | V00034 | GND | N | | GD03986 | S.. | N | | 050-099, 155-199, 276-299 |
| 024 | 18 | | UA | | 2-1 | 32-42-11 | V00034 | GND | N | | GD03986 | S.. | N | | 150-154, 275 |
| 025 | 18 | | UA | | 2-4 | 32-42-11 | V00036 | GND | N | | GD03986 | S.. | N | | ALL |
| 026 | 18 | | UA | | 2-3 | 32-42-11 | V00040 | GND | N | | GD03988 | S.. | N | | ALL |
| 027 | 18 | | UA | | 2-2 | 28-31-11 | GD03334 | D.. | N | | D12182 | 4 | | | 050-099, 155-199, 276-299 |
| 028 | 18 | | UA | | 1-11 | 28-31-11 | GD03336 | S.. | N | | D12182 | 7 | | | 050-099, 155-199, 276-299 |
| 029 | 18 | | UA | | 1-11 | 28-31-12 | GD05824 | D.. | N | | D12186 | 4 | | | 050-099, 155-199, 276-299 |
| 030 | 18 | | UA | | 1-9 | 28-31-12 | GD05820 | S.. | N | | D12186 | 7 | | | 050-099, 155-199, 276-299 |
| 031 | 18 | | UA | | 2-6 | 28-42-13 | GD03328 | D.. | N | | D12194 | 2 | DK | | 155-157, 165-199, 277-299 |
| 032 | 18 | | UA | | 2-7 | 28-42-13 | GD03330 | S.. | N | | D12194 | 4 | DK | | 155-157, 165-199, 277-299 |
| 100 | 20 | | VF | DY | 14-2 | 28-42-13 | D08376P | 7 | | | D12194 | 3 | | | 155-157, 165-199, 277-299 |
| 100Z | | | | DY | 0-0 | 28-42-13 | GD04140 | S.. | N | | GD04108 | S.. | N | | 155-157, 165-199, 277-299 |
| 201B | 18 | | VG | A | 26-3 | 25-65-12 | D01166 | 3 | | | D04278P | 8 | | | 050-099, 155-199, 276-299 |
| 201B | 18 | | VG | A | 26-4 | 25-65-12 | D01166 | 3 | | | D04278P | 8 | | | 150-154, 275 |
| 201R | 18 | | VG | A | 0-0 | 25-65-12 | D01166 | 4 | | | D04278P | 9 | | | ALL |
| 201Z | | | | A | 0-0 | 25-65-12 | GD03934 | S.. | N | | GD03990 | S.. | N | | ALL |
| 202B | 20 | | VG | C | 20-1 | 32-42-11 | D04278P | 2 | | | D02038 | 1 | | | ALL |
| 202R | 20 | | VG | C | 0-0 | 32-42-11 | D04278P | 5 | | | D02038 | 2 | | | ALL |
| 202Z | | | | C | 0-0 | 32-42-11 | GD04044 | S.. | N | | GD04100 | S.. | N | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0450
Page 6
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------|--|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0452 | 286T0452 | | | | R WING REAR SPAR -R2B- ANTI-SKID/FUEL (continued) | | | | | | | | | | |
| 203B | 20 | VG | D | 20-4 | 32-42-11 | D04278P | | 3 | | | D02042 | | 1 | | 050-099, 155-199, 276-299 |
| 203B | 20 | VG | D | 20-5 | 32-42-11 | D04278P | | 3 | | | D02042 | | 1 | | 150-154, 275 |
| 203R | 20 | VG | D | 0-0 | 32-42-11 | D04278P | | 6 | | | D02042 | | 2 | | ALL |
| 203Z | | | D | 0-0 | 32-42-11 | GD03990 | | S.. | N | | GD04100 | | S.. | N | ALL |
| 204B | 20 | VG | E | 25-3 | 32-42-11 | D04278P | | 4 | | | D02050 | | 1 | | 050-099, 155-199, 276-299 |
| 204B | 20 | VG | E | 25-4 | 32-42-11 | D04278P | | 4 | | | D02050 | | 1 | | 150-154, 275 |
| 204R | 20 | VG | E | 0-0 | 32-42-11 | D04278P | | 7 | | | D02050 | | 2 | | ALL |
| 204Z | | | E | 0-0 | 32-42-11 | GD03990 | | S.. | N | | GD03782 | | S.. | N | ALL |
| 300B | 20 | VH | LY | 67-6 | 28-31-12 | D08376P | | 4 | | | D12186 | | 5 | | 050-099, 155-199, 276-299 |
| 300R | 20 | VH | LY | 0-0 | 28-31-12 | D08376P | | 5 | | | D12186 | | 2 | | 050-099, 155-199, 276-299 |
| 300Y | 20 | VH | LY | 0-0 | 28-31-12 | D08376P | | 6 | | | D12186 | | 3 | | 050-099, 155-199, 276-299 |
| 300Z | | | LY | 0-0 | 28-31-12 | GD03946 | | S.. | N | | GD05820 | | S.. | N | 050-099, 155-199, 276-299 |
| 301B | 20 | VH | B | 28-2 | 29-31-11 | D04278P | | 15 | | | D00058 | | 1 | | 050-099, 155-199, 276-299 |
| 301B | 20 | VH | B | 28-7 | 29-31-11 | D04278P | | 15 | | | D00058 | | 1 | | 150-154, 275 |
| 301R | 20 | VH | B | 0-0 | 29-31-11 | D04278P | | 16 | | | D00058 | | 2 | | ALL |
| 301Y | 20 | VH | B | 0-0 | 29-31-11 | D04278P | | 17 | | | D00058 | | 3 | | ALL |
| 301Z | | | B | 0-0 | 29-31-11 | GD03990 | | S.. | N | | GD04084 | | S.. | N | ALL |
| 302B | 20 | VH | MB | 14-9 | 28-31-11 | D08376P | | 2 | | | D12182 | | 5 | | 050-099, 155-199, 276-299 |
| 302R | 20 | VH | MB | 0-0 | 28-31-11 | D08376P | | 3 | | | D12182 | | 2 | | 050-099, 155-199, 276-299 |
| 302Y | 20 | VH | MB | 0-0 | 28-31-11 | D08376P | | 1 | | | D12182 | | 3 | | 050-099, 155-199, 276-299 |
| 302Z | | | MB | 0-0 | 28-31-11 | GD04044 | | S.. | N | | GD03438 | | S.. | N | 050-099, 155-199, 276-299 |
| W0453 | 286T0453 | | | | CAUTION & WARNING R.,PANEL TO SHELVES | | | | | | | | | | |
| 001 | 24 | PK | | 22-0 | 23-21-11 | D04819J | | 17 | | | D04349P | | 17 | | ALL |
| 002 | 24 | PK | | 28-0 | 27-32-21 | D04325J | | 6 | | | D04349P | | 6 | | ALL |
| 003 | 24 | PK | | 22-0 | 31-51-41 | D04819J | | 52 | | | D04349P | | 3 | | ALL |
| 004 | 24 | PK | | 22-0 | 31-51-21 | D04819J | | 9 | | | D04349P | | 9 | | ALL |
| 005 | 24 | PK | | 22-0 | 31-51-33 | D04819J | | 13 | | | D04349P | | 13 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0450
Page 7
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0453 | 286T0453 | | | CAUTION & WARNING R., PANEL TO SHELVES (continued) | | | | | | | | | | | | |
| 006 | 24 | | PK | 12-0 | 31-51-21 | SP00495 | | | | S | | D04349P | 5 | | | 050-099, 155-199, 276-299 |
| 006 | 24 | | PK | 22-0 | 31-51-21 | D04819J | | 5 | | | | D04349P | 5 | | | 150-154, 275 |
| 007 | 24 | | PK | 12-0 | 31-51-21 | SP00499 | | | | S | | D04349P | 4 | | | 050-099, 155-199, 276-299 |
| 007 | 24 | | PK | 22-0 | 31-51-21 | D04819J | | 4 | | | | D04349P | 4 | | | 150-154, 275 |
| 008 | 24 | | PK | 12-0 | 31-51-21 | SP00501 | | | | S | | D04349P | 12 | | | 050-099, 155-199, 276-299 |
| 008 | 24 | | PK | 22-0 | 31-51-21 | D04819J | | 12 | | | | D04349P | 12 | | | 150-154, 275 |
| 009 | 24 | | PK | 22-0 | SPARE | D04819J | | 1 | | | | D04349P | 1 | | | ALL |
| 010 | 24 | | PK | 22-0 | 31-51-33 | D04819J | | 2 | | | | D04349P | 2 | | | ALL |
| 011 | 24 | | PK | 28-0 | 31-51-42 | D04325J | | 12 | | | | D04349P | 22 | | | ALL |
| 012 | 24 | | PK | 28-0 | 31-51-41 | D04325J | | 7 | | | | D04349P | 7 | | | ALL |
| 014 | 20 | | PA | 12-0 | 27-32-21 | SM00001 | | | | S | | D04325J | 13 | | | ALL |
| 015 | 24 | | PK | 28-0 | 31-51-11 | D04349P | | 32 | | | | D04325J | 14 | | | ALL |
| 016 | 20 | | PA | 4-0 | 31-51-11 | D04349P | | 33 | | | | GD00301 | A.. | 2 | | ALL |
| 017 | 24 | | PK | 22-0 | 27-32-11 | D04349P | | 14 | | | | D04819J | 24 | | | ALL |
| 018 | 24 | | PK | 22-0 | 27-32-11 | D04349P | | 15 | | | | D04819J | 36 | | | ALL |
| 019 | 24 | | PK | 22-0 | 27-32-11 | D04349P | | 16 | | | | D04819J | 37 | | | ALL |
| 020 | 24 | | PK | 22-0 | 27-32-11 | D04349P | | 10 | | | | D04819J | 38 | | | ALL |
| 021 | 24 | | PK | 22-0 | 27-32-21 | D04349P | | 34 | | | | D04819J | 39 | | | ALL |
| 022 | 24 | | PK | 22-0 | 27-32-21 | D04349P | | 35 | | | | D04819J | 40 | | | ALL |
| 023 | 24 | | PK | 22-0 | 27-32-21 | D04349P | | 36 | | | | D04819J | 35 | | | ALL |
| 024 | 24 | | PK | 22-0 | 27-32-21 | D04349P | | 37 | | | | D04819J | 41 | | | ALL |
| 025 | 24 | | PK | 18-6 | 34-61-23 | D04809P | | 2 | | | | D04819J | 25 | | | ALL |
| 026 | 24 | | PK | 18-6 | 34-61-23 | D04809P | | 3 | | | | D04819J | 26 | | | ALL |
| 027 | 24 | | PK | 18-6 | 34-61-23 | D04809P | | 4 | | | | D04819J | 27 | | | ALL |
| 028 | 24 | | PK | 18-6 | 34-61-23 | D04809P | | 5 | | | | D04819J | 28 | | | ALL |
| 029 | 24 | | PV | 18-6 | 34-61-23 | D04809P | | 6 | | | | D04819J | 29 | | | ALL |
| 029Z | | | BD | 0-0 | 34-61-23 | D04809P | | | DED | | | D04819J | DED | | | ALL |
| 030 | 24 | | PV | 18-6 | 34-61-23 | D04809P | | 7 | | | | D04819J | 30 | | | ALL |
| 030Z | | | BE | 0-0 | 34-61-23 | D04809P | | | DED | | | D04819J | DED | | | ALL |
| 031 | 24 | | PV | 18-6 | 34-61-23 | D04809P | | 8 | | | | D04819J | 31 | | | ALL |
| 031Z | | | BF | 0-0 | 34-61-23 | D04809P | | | DED | | | D04819J | DED | | | ALL |
| 032 | 24 | | PV | 18-6 | 34-61-23 | D04809P | | 9 | | | | D04819J | 32 | | | ALL |
| 032Z | | | BG | 0-0 | 34-61-23 | D04809P | | | DED | | | D04819J | DED | | | ALL |
| 033 | 24 | | PV | 18-6 | 34-61-23 | D04809P | | 10 | | | | D04819J | 33 | | | ALL |
| 033Z | | | BH | 0-0 | 34-61-23 | D04809P | | | DED | | | D04819J | DED | | | ALL |
| 034 | 24 | | PK | 18-6 | 34-61-23 | D04809P | | 1 | | | | D04819J | 34 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0450
Page 8
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0453 | 286T0453 | | | CAUTION & WARNING R.,PANEL TO SHELVES (continued) | | | | | | | | | | | | | |
| 035 | 24 | | PK | 22-0 | 31-51-11 | D04349P | | 38 | | | | | D04819J | 3 | | | ALL |
| 036 | 24 | | PK | 22-0 | 31-51-21 | D04349P | | 39 | | | | | D04819J | 10 | | | ALL |
| 037 | 24 | | PK | 22-0 | 31-51-33 | D04349P | | 40 | | | | | D04819J | 11 | | | ALL |
| 038 | 24 | | PK | 28-0 | 31-51-41 | D04325J | | 21 | | | | | D04349P | 21 | | | ALL |
| 039 | 24 | | PK | 22-0 | 31-51-41 | D04349P | | 24 | | | | | D04819J | 21 | | | ALL |
| 040 | 24 | | PK | 22-0 | 27-81-31 | D04819J | | CAP | Y | | | | D04349P | 23 | | | 050-099, 150-166 |
| 040 | 24 | | PK | 22-0 | SPARE | D04819J | | CAP | Y | | | | D04349P | 23 | | | 167-199, 275-299 |
| 042 | 24 | | PK | 12-0 | 31-51-41 | D04809P | | 12 | | | | | D04349P | 31 | | | ALL |
| 043 | 24 | | PK | 12-0 | SPARE | D04809P | | 13 | | | | | D04349P | 41 | | | ALL |
| 045 | 24 | | PK | 22-0 | 31-51-21 | D04819J | | 22 | | | | | D04349P | 44 | | | ALL |
| 048 | 24 | | PK | 22-0 | 27-81-31 | D04819J | | 23 | | | | | D04349P | 8 | | | ALL |
| 050 | 22 | | PA | 28-0 | SPARE | D04349P | | 20 | | | | | D04325J | 4 | | | ALL |
| 051 | 20 | | PA | 28-0 | 38-32-11 | D04349P | | 26 | | | | | D04325J | 5 | | | 050-099, 150-199, 277-299 |
| 051 | 22 | | PA | 28-0 | SPARE | D04349P | | 26 | | | | | D04325J | 5 | | | 275 |
| 051 | 20 | | PA | 28-0 | SPARE | D04349P | | 26 | | | | | D04325J | 5 | | | 276 |
| 053 | 22 | | PA | 18-6 | SPARE | D04809P | | 23 | | | | | D04819J | 54 | | | 050-099 |
| 053 | 22 | | PA | 18-6 | 31-51-42 | D04809P | | 23 | | | | | D04819J | 54 | | | 150-199, 275-299 |
| 055 | 24 | | PK | 22-0 | 31-41-16 | D04819J | | 15 | | | | | D04349P | 30 | | | ALL |
| 056 | 24 | | PK | 12-0 | 31-51-21 | SP00497 | | | | S | | | D04349P | 29 | | | 050-099, 155-199, 276-299 |
| 056 | 24 | | PK | 22-0 | 31-51-21 | D04819J | | 14 | | | | | D04349P | 29 | | | 150-154, 275 |
| 057 | 20 | | PQ | CG | 22-0 | 27-32-31 | | 44 | | | | | D04349P | 42 | | | ALL |
| 057Z | | | | CG | 0-0 | 27-32-31 | | | DED | | | | D04349P | DED | | | ALL |
| 058 | 24 | | PK | | 12-0 | SPARE | | 15 | | | | | D04349P | 43 | | | ALL |
| 060 | 24 | | PK | | 12-0 | SPARE | | 16 | | | | | D04349P | 45 | | | ALL |
| 061 | 20 | | PA | | 17-0 | 27-32-21 | | 11 | | | | | SM00001 | | S | | ALL |
| 062 | 24 | | PK | | 6-0 | 31-31-22 | | 43 | | | | | SM00001 | | S | | ALL |
| 063 | 24 | | PK | | 19-0 | 31-31-21 | | 49 | | | | | D04809P | 17 | | | ALL |
| 064 | 24 | | PK | | 19-0 | 31-31-21 | | 50 | | | | | D04809P | 18 | | | ALL |
| 201 | 20 | | UA | | 4-0 | 27-32-21 | | S.. | 2 | | | | D04349P | | | IA | ALL |
| 201B | 24 | | PW | IA | 22-0 | 27-32-21 | | 8 | | | | | D04349P | 28 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 27-32-21 | | 7 | | | | | D04349P | 27 | | | ALL |
| 201Z | | | | IA | 0-0 | 27-32-21 | | 6 | | | | | D04349P | | | IA | ALL |
| 205 | 20 | | UA | | 4-0 | 22-14-21 | | S.. | 2 | | | | D04349P | | | IE | ALL |
| 205B | 24 | | PW | IE | 22-0 | 22-14-21 | | 19 | | | | | D04349P | 19 | | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 22-14-21 | | 18 | | | | | D04349P | 18 | | | ALL |
| 205Z | | | | IE | 0-0 | 22-14-21 | | 20 | | | | | D04349P | | | IE | ALL |
| 206B | 22 | | PB | IF | 22-0 | 31-51-43 | | 47 | | | | | D04349P | 47 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0450

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0453 | 286T0453 | | | CAUTION & WARNING R., PANEL TO SHELVES (continued) | | | | | | | | | | | |
| 206R | 22 | | PB | IF | 0-0 | 31-51-43 | D04819J | | 46 | | D04349P | | 46 | | ALL |
| 207 | 20 | | UA | | 4-0 | 27-32-21 | D04349P | | | IG | GD00727 | | S.. | 2 | ALL |
| 207B | 24 | | PW | IG | 22-0 | 27-32-21 | D04679J | | 2 | | D04349P | | 55 | | ALL |
| 207R | 24 | | PW | IG | 0-0 | 27-32-21 | D04679J | | 1 | | D04349P | | 54 | | ALL |
| 207Z | | | | IG | 0-0 | 27-32-21 | D04679J | | 3 | | D04349P | | | IG | ALL |
| 208 | 20 | | UA | | 4-0 | 27-32-21 | D04349P | | | IH | GD00727 | | S.. | 2 | ALL |
| 208B | 24 | | PW | IH | 28-0 | 27-32-21 | D04325J | | 23 | | D04349P | | 49 | | ALL |
| 208R | 24 | | PW | IH | 0-0 | 27-32-21 | D04325J | | 22 | | D04349P | | 48 | | ALL |
| 208Z | | | | IH | 0-0 | 27-32-21 | D04325J | | 24 | | D04349P | | | IH | ALL |
| 209 | 20 | | UA | | 4-0 | 27-32-21 | D04349P | | | II | GD00727 | | S.. | 2 | ALL |
| 209B | 24 | | PW | II | 22-0 | 27-32-21 | D04679J | | 5 | | D04349P | | 52 | | ALL |
| 209R | 24 | | PW | II | 0-0 | 27-32-21 | D04679J | | 4 | | D04349P | | 51 | | ALL |
| 209Z | | | | II | 0-0 | 27-32-21 | D04679J | | 6 | | D04349P | | | II | ALL |
| 210B | 24 | | PL | IJ | 28-0 | 27-32-21 | D04325J | | 18 | | D04349P | | 53 | | ALL |
| 210R | 24 | | PL | IJ | 0-0 | 27-32-21 | D04325J | | 17 | | D04349P | | 50 | | ALL |
| 211B | 24 | | PW | IK | 22-0 | 31-41-35 | D04349P | | 57 | | D04819J | | 45 | | ALL |
| 211R | 24 | | PW | IK | 0-0 | 31-41-35 | D04349P | | 56 | | D04819J | | 42 | | ALL |
| 211Z | | | | IK | 0-0 | 31-41-35 | D04349P | | 58 | | D04819J | | 48 | | ALL |
| 212B | 24 | | PW | IL | 22-0 | 28-41-11 | D04349P | | 60 | | D04819J | | 53 | | ALL |
| 212R | 24 | | PW | IL | 0-0 | 28-41-11 | D04349P | | 59 | | D04819J | | 51 | | ALL |
| 212Z | | | | IL | 0-0 | 28-41-11 | D04349P | | 61 | | D04819J | | 55 | | ALL |
| 903B | 24 | | PW | AA | 0-0 | 34-53-21 | D04679J | | 8 | | D04325J | | 9 | | 275-299 |
| 903R | 24 | | PW | AA | 10-0 | 34-53-21 | D04679J | | 7 | | D04325J | | 8 | | 275-299 |
| 903Z | | | | AA | 0-0 | 34-53-21 | D04679J | | 9 | | D04325J | | 10 | | 275-299 |
| W0454 | 286T0454 | | | L WING REAR SPAR-S2A-FUEL | | | | | | | | | | | |
| 003 | 18 | | UA | | 2-0 | 28-21-13 | D01614 | | 1 | DK | GD03382 | | D.. | N | ALL |
| 004 | 18 | | UA | | 2-0 | 28-21-13 | D01614 | | 4 | DK | GD03382 | | D.. | N | ALL |
| 005 | 18 | | UA | | 2-0 | 28-21-13 | D01614 | | 3 | DK | GD03384 | | S.. | N | ALL |
| 008 | 18 | | VF | B | 4-0 | 28-22-21 | D01554 | | 6 | | SP00464 | | | 9 | ALL |
| 008Z | | | | B | 0-0 | 28-22-21 | GD04066 | | S.. | N | SP01948 | | | 9 | ALL |
| 009 | 18 | | UA | | 5-0 | 28-22-21 | D01554 | | 4 | | GD03386 | | D.. | N | ALL |
| 012 | 18 | | UA | | 13-0 | 28-22-31 | D01544 | | 4 | | D04602P | | 4 | | 050-099, 155-199, 276-299 |
| 012 | 18 | | UA | | 4-0 | 28-22-31 | D01544 | | 4 | | D04602P | | 4 | | 150-154, 275 |
| 013 | 18 | | UA | | 4-0 | 28-42-21 | D01566 | | 2 | DK | GD03390 | | D.. | N | ALL |
| 014 | 20 | | VF | F | 15-0 | 28-42-21 | D01566 | | 1 | | D04602P | | 7 | | ALL |
| 014Z | | | | F | 0-0 | 28-42-21 | GD04606 | | S.. | N | GD04134 | | S.. | N | ALL |
| 015 | 18 | | UA | | 4-0 | 28-42-21 | D01566 | | 4 | DK | GD03392 | | S.. | N | ALL |

WIRE LIST

D280T132

91-21-11
Section W0450
Page 10
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|----------|--------|------|--------|-------|------|---------|--------|-------------|-----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0454 | 286T0454 | | | L WING REAR SPAR-S2A-FUEL (continued) | | | | | | | | | | | | | |
| 026 | 18 | | UA | 4-0 | 28-22-21 | D01554 | | 7 | | | | | GD03396 | S.. | N | | ALL |
| 027 | 18 | | UA | 13-0 | 28-22-31 | D01544 | | 7 | | | | | GD04134 | S.. | N | | 050-099, 155-199, 277-299 |
| 027 | 18 | | UA | 4-0 | 28-22-31 | D01544 | | 7 | | | | | GD04134 | S.. | N | | 150-154, 275 |
| 027 | 18 | | UA | 15-0 | 28-22-31 | D01544 | | 7 | | | | | GD04134 | S.. | N | | 276 |
| 032 | 18 | | UA | 13-0 | 28-22-31 | D01544 | | 5 | | | | | D04602P | | | 16 | 050-099, 155-199, 277-299 |
| 032 | 18 | | UA | 15-0 | 28-22-31 | D01544 | | 5 | | | | | D04602P | | | 16 | 150-154, 275-276 |
| 033 | 18 | | UA | 13-0 | 28-22-31 | D01544 | | 2 | | | | | D04602P | | | 15 | 050-099, 155-199, 277-299 |
| 033 | 18 | | UA | 15-0 | 28-22-31 | D01544 | | 2 | | | | | D04602P | | | 15 | 150-154, 275-276 |
| 034 | 18 | | UA | 13-0 | 28-22-31 | D01544 | | 3 | | | | | D04602P | | | 3 | 050-099, 155-199, 277-299 |
| 034 | 18 | | UA | 15-0 | 28-22-31 | D01544 | | 3 | | | | | D04602P | | | 3 | 150-154, 275-276 |
| 0BLK | 20 | | 8Y | G | 15-0 | 28-41-23 | D02816 | | 5 | | | | D05884P | | | 6 | ALL |
| 0BLU | 20 | | 8Y | G | 0-0 | 28-41-23 | D02816 | | 2 | | | | D05884P | | | 3 | ALL |
| 0GRN | 20 | | 8Y | G | 0-0 | 28-41-23 | D02816 | | 4 | | | | D05884P | | | 5 | ALL |
| 0RED | 20 | | 8Y | G | 0-0 | 28-41-23 | D02816 | | 1 | | | | D05884P | | | 2 | ALL |
| 0YEL | 20 | | 8Y | G | 0-0 | 28-41-23 | D02816 | | 3 | | | | D05884P | | | 4 | ALL |
| 19TI | | | | H | 0-0 | 28-41-23 | D02812 | | =C1 | | | | D06078P | | | =C1 | ALL |
| 19TO | | | | H | 0-0 | 28-41-23 | GD04132 | | S.. | N | | | GD04034 | | | S.. | N |
| 19TX | | | | 8X | H | 14-0 | 28-41-23 | D02812 | | 1 | | | D06078P | | | 1 | ALL |
| 201B | 20 | | VG | C | 20-0 | 28-21-13 | D01614 | | 2 | | | | D04602P | | | 1 | ALL |
| 201R | 20 | | VG | C | 0-0 | 28-21-13 | D01614 | | 5 | | | | D04602P | | | 2 | ALL |
| 201Z | | | | C | 0-0 | 28-21-13 | GD03384 | | S.. | N | | | GD04134 | | | S.. | N |
| 302B | 20 | | VH | E | 23-0 | 28-22-21 | D01554 | | 5 | | | | D04602P | | | 13 | ALL |
| 302R | 20 | | VH | E | 0-0 | 28-22-21 | D01554 | | 2 | | | | D04602P | | | 14 | ALL |
| 302Y | 20 | | VH | E | 0-0 | 28-22-21 | D01554 | | 3 | | | | D04602P | | | 5 | ALL |
| 302Z | | | | E | 0-0 | 28-22-21 | GD04066 | | S.. | N | | | GD04134 | | | S.. | N |
| BLKZ | | | | G | 0-0 | 28-41-23 | GD04132 | | S.. | N | | | GD04034 | | | S.. | N |
| W0455 | 286T0455 | | | FMC & PACS,P61 TO E1 | | | | | | | | | | | | | |
| 001 | 24 | | PK | 25-0 | 22-11-32 | D04541P | | 1 | | | | | D04543J | | | 1 | ALL |
| 002 | 24 | | PK | 25-0 | 22-11-32 | D04541P | | 2 | | | | | D04543J | | | 2 | ALL |
| 003 | 18 | | PA | 25-0 | SPARE | D04541P | | 14 | | | | | D04543J | | | 14 | ALL |
| 004 | 22 | | PA | 25-0 | SPARE | D04541P | | 4 | | | | | D04543J | | | 4 | ALL |
| 005 | 24 | | PK | 25-0 | 22-41-11 | D04541P | | 5 | | | | | D04543J | | | 5 | ALL |
| 006 | 12 | | PA | 25-0 | SPARE | D04541P | | 16 | | | | | D04543J | | | 16 | ALL |
| 007 | 22 | | PA | 25-0 | SPARE | D04541P | | 7 | | | | | D04543J | | | 7 | ALL |

WIRE LIST

D280T132

91-21-11

Section W0450

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0456 | 286T0456 | | | R WING REAR SPAR -S2A- FUEL | | | | | | | | | | | | | |
| 006 | 18 | | UA | | 1-5 | 28-21-13 | D01620 | | 3 | DK | | | GD03400 | S.. | N | | ALL |
| 009 | 18 | | UA | | 2-11 | 28-21-13 | D01616 | | 1 | DK | | | GD03402 | D.. | N | | ALL |
| 010 | 18 | | UA | | 2-11 | 28-21-13 | D01616 | | 4 | DK | | | GD03402 | D.. | N | | ALL |
| 011 | 18 | | UA | | 2-10 | 28-21-13 | D01616 | | 3 | DK | | | GD03404 | S.. | N | | ALL |
| 014 | 18 | | UA | | 2-0 | 28-26-11 | D01256 | | 4 | | | | GD03406 | D.. | N | | ALL |
| 015 | 18 | | VF | C | 78-6 | 27-11-22 | D01636 | | 3 | | | | D05520P | | 19 | | ALL |
| 015Z | | | | C | 0-0 | 27-11-22 | GD03410 | | S.. | N | | | GD03972 | S.. | N | | ALL |
| 016 | 18 | | UA | | 1-8 | 27-11-22 | D01636 | | 6 | | | | GD03410 | S.. | N | | ALL |
| 022 | 18 | | VF | A | 3-7 | 28-22-21 | D01572 | | 6 | | | | SP00466 | | 9 | | ALL |
| 022Z | | | | A | 0-0 | 28-22-21 | GD04062 | | S.. | N | | | SP01944 | | 9 | | ALL |
| 023 | 18 | | UA | | 6-9 | 28-22-21 | D01572 | | 4 | | | | GD03414 | D.. | N | | ALL |
| 024 | 18 | | UA | | 6-5 | 28-22-21 | D01572 | | 7 | | | | GD03422 | S.. | N | | ALL |
| 025 | 18 | | UA | | 1-11 | 28-26-11 | D01256 | | 7 | | | | GD03490 | S.. | N | | ALL |
| 201B | 20 | | VG | F | 19-1 | 28-21-13 | D01616 | | 2 | | | | D05520P | | 5 | | ALL |
| 201R | 20 | | VG | F | 0-0 | 28-21-13 | D01616 | | 5 | | | | D05520P | | 4 | | ALL |
| 201Z | | | | F | 0-0 | 28-21-13 | GD04318 | | S.. | N | | | GD03944 | S.. | N | | ALL |
| 302B | 20 | | VH | G | 20-7 | 28-22-21 | D01572 | | 5 | | | | D05520P | | 1 | | ALL |
| 302R | 20 | | VH | G | 0-0 | 28-22-21 | D01572 | | 2 | | | | D05520P | | 15 | | ALL |
| 302Y | 20 | | VH | G | 0-0 | 28-22-21 | D01572 | | 3 | | | | D05520P | | 17 | | ALL |
| 302Z | | | | G | 0-0 | 28-22-21 | GD04062 | | S.. | N | | | GD03972 | S.. | N | | ALL |
| 303B | 20 | | VH | H | 19-0 | 28-26-11 | D01256 | | 2 | | | | D05520P | | 6 | | ALL |
| 303R | 20 | | VH | H | 0-0 | 28-26-11 | D01256 | | 5 | | | | D05520P | | 7 | | ALL |
| 303Y | 20 | | VH | H | 0-0 | 28-26-11 | D01256 | | 3 | | | | D05520P | | 18 | | ALL |
| 303Z | | | | H | 0-0 | 28-26-11 | GD03490 | | S.. | N | | | GD03972 | S.. | N | | ALL |
| 401B | 20 | | U4 | D | 78-6 | 27-11-22 | D01636 | | 4 | | | | D05520P | | 13 | | ALL |
| 401G | 20 | | U4 | D | 0-0 | 27-11-22 | D01636 | | 2 | | | | D05520P | | 12 | | ALL |
| 401R | 20 | | U4 | D | 0-0 | 27-11-22 | D01636 | | 1 | | | | D05520P | | 11 | | ALL |
| 401Y | 20 | | U4 | D | 0-0 | 27-11-22 | D01636 | | 5 | | | | D05520P | | 14 | | ALL |
| 401Z | | | | D | 0-0 | 27-11-22 | GD03410 | | S.. | N | | | GD03944 | S.. | N | | ALL |
| 402B | 20 | | U4 | E | 44-9 | 28-21-13 | D01620 | | 5 | | | | D05520P | | 2 | | ALL |
| 402G | 20 | | U4 | E | 0-0 | 28-21-13 | D01620 | | 2 | | | | D05520P | | 3 | | ALL |
| 402R | 20 | | U4 | E | 0-0 | 28-21-13 | D01620 | | 1 | | | | D05520P | | 20 | | ALL |
| 402Y | 20 | | U4 | E | 0-0 | 28-21-13 | D01620 | | 4 | | | | D05520P | | 21 | | ALL |
| 402Z | | | | E | 0-0 | 28-21-13 | GD03400 | | S.. | N | | | GD03944 | S.. | N | | ALL |
| W0458 | 286T0458 | | | L WING REAR SPAR-S2B-FUEL/FLT CONT | | | | | | | | | | | | | |
| 001 | 18 | | VF | A | 19-6 | 28-22-21 | SP00464 | | | | | | SP01754 | | 9 | | ALL |
| 001Z | | | | A | 0-0 | 28-22-21 | SP01948 | | | | | | SP01946 | | 9 | | ALL |
| 004 | 18 | | UA | | 2-3 | 28-26-11 | D01254 | | 4 | | | | GD03394 | D.. | N | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0450
Page 12
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|-----------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0458 | 286T0458 | | | L WING REAR SPAR-S2B-FUEL/FLT CONT (continued) | | | | | | | | | | | |
| 007 | 18 | UA | | 2-1 | 28-26-11 | D01254 | 7 | | | GD03488 | S.. | N | | ALL | |
| 301B | 20 | VH | B | 20-10 | 28-26-11 | D01254 | 3 | | | D04612P | 3 | | | ALL | |
| 301R | 20 | VH | B | 0-0 | 28-26-11 | D01254 | 2 | | | D04612P | 1 | | | ALL | |
| 301Y | 20 | VH | B | 0-0 | 28-26-11 | D01254 | 5 | | | D04612P | 2 | | | ALL | |
| 301Z | | | B | 0-0 | 28-26-11 | GD03396 | S.. | N | | GD04034 | S.. | N | | ALL | |
| W0459 | 286T0459 | | | AFCS MODE CONT L,SHELF AND PNLS TO CONT PNL | | | | | | | | | | | |
| 001 | 22 | PA | | 22-0 | 22-11-12 | D04591J | 1 | | | D05419J | 1 | | | ALL | |
| 002 | 22 | PA | | 22-0 | 22-11-12 | D04591J | 2 | | | D05419J | 2 | | | ALL | |
| 003 | 22 | PA | | 22-0 | 22-11-12 | D04591J | 3 | | | D05419J | 3 | | | ALL | |
| 007 | 24 | PK | | 22-0 | 22-32-15 | D04591J | 13 | | | D05419J | 13 | | | ALL | |
| 008 | 24 | PK | | 22-0 | 22-32-15 | D04591J | 14 | | | D05419J | 14 | | | ALL | |
| 010 | 24 | PK | | 33-0 | 31-51-31 | D05419J | 16 | | | D04597P | 10 | | | ALL | |
| 013 | 20 | PA | | 3-0 | 31-51-31 | D04597P | 14 | | | GD00301 | S.. | 2 | | ALL | |
| 014 | 24 | PK | | 9-0 | 31-51-11 | D00697 | 4 | | | SP00037 | | 9 | | ALL | |
| 017 | 24 | PK | | 33-0 | SPARE | D05419J | 17 | | | D04597P | 6 | | | ALL | |
| 025 | 24 | PK | | 23-0 | SPARE | D04591J | 15 | | | D04597P | 15 | | | ALL | |
| 026 | 22 | PA | | 22-0 | SPARE | D04591J | 18 | | | D05419J | 18 | | | ALL | |
| 027 | 22 | PA | | 22-0 | SPARE | D04591J | 19 | | | D05419J | 19 | | | ALL | |
| 028 | 24 | PK | | 23-0 | SPARE | D04591J | 20 | | | D04597P | 1 | | | ALL | |
| 201B | 24 | PW | IA | 22-0 | 22-12-11 | D04591J | 5 | | | D05419J | 5 | | | ALL | |
| 201R | 24 | PW | IA | 0-0 | 22-12-11 | D04591J | 4 | | | D05419J | 4 | | | ALL | |
| 201Z | | | IA | 0-0 | 22-12-11 | D04591J | 6 | | | D05419J | 6 | | | ALL | |
| 202B | 24 | PW | IB | 22-0 | 22-13-11 | D04591J | 8 | | | D05419J | 8 | | | ALL | |
| 202R | 24 | PW | IB | 0-0 | 22-13-11 | D04591J | 7 | | | D05419J | 7 | | | ALL | |
| 202Z | | | IB | 0-0 | 22-13-11 | D04591J | 9 | | | D05419J | 9 | | | ALL | |
| 203B | 24 | PW | IC | 22-0 | 22-14-11 | D04591J | 11 | | | D05419J | 11 | | | ALL | |
| 203R | 24 | PW | IC | 0-0 | 22-14-11 | D04591J | 10 | | | D05419J | 10 | | | ALL | |
| 203Z | | | IC | 0-0 | 22-14-11 | D04591J | 12 | | | D05419J | 12 | | | ALL | |
| 207 | 20 | UA | | 1-6 | 31-51-21 | GD00301 | S.. | 2 | | D04597P | | | IG | 050-099 | |
| 207 | 20 | UA | | 3-0 | 31-51-21 | GD00301 | S.. | 2 | | D04597P | | | IG | 150-199, 275-299 | |
| 207B | 24 | PW | IG | 23-0 | 31-51-21 | D04591J | 22 | | | D04597P | 4 | | | ALL | |
| 207R | 24 | PW | IG | 0-0 | 31-51-21 | D04591J | 21 | | | D04597P | 3 | | | ALL | |
| 207Z | | | IG | 0-0 | 31-51-21 | D04591J | 23 | | | D04597P | | | IG | ALL | |
| 209B | 22 | PB | II | 3-0 | 31-51-31 | D04597P | 5 | | | GD00727 | S.. | 2 | | 150-152, 157, 167-199, 275-278 | |
| 209R | 22 | PB | II | 0-0 | 31-51-31 | D04597P | 2 | | | GD00727 | S.. | 2 | | 150-152, 157, 167-199, 275-278 | |

WIRE LIST

D280T132

91-21-11

Section W0450

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | To | | | | |
|--------------|-----------------|-------------|----|-----|--|----------|---------|------|------|--------|---------|---------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0459 | 286T0459 | | | | AFCS MODE CONT L,SHELF AND PNLs TO CONT PNL (continued) | | | | | | | | | | |
| 224B | 22 | | PR | IX | 23-0 | 34-45-13 | D04597P | | | 5 | | | | | 050-099, 153-156, 162-166, 280-299 |
| 224B | 22 | | PR | IX | 23-0 | 34-45-13 | D04597P | CAP | Y | | D04591J | | | 17 | 150-152, 275-276 |
| 224B | 22 | | PR | IX | 23-0 | 34-45-13 | D04597P | REF | JW | | D04591J | | | 28 | 157, 167-199, 277-278 |
| 224R | 22 | | PR | IX | 0-0 | 34-45-13 | D04597P | | | 2 | D04591J | | | 27 | 050-099, 153-156, 162-166, 280-299 |
| 224R | 22 | | PR | IX | 0-0 | 34-45-13 | D04597P | CAP | Y | | D04591J | | | 16 | 150-152, 275-276 |
| 224R | 22 | | PR | IX | 0-0 | 34-45-13 | D04597P | REF | JW | | D04591J | | | 27 | 157, 167-199, 277-278 |
| 224Z | | | | IX | 0-0 | 34-45-13 | D04597P | | | 9 | D04591J | | | 29 | 050-099, 155-156, 162-166, 280-299 |
| 224Z | | | | IX | 0-0 | 34-45-13 | D04597P | DED | | | D04591J | | | 24 | 150-152, 275-276 |
| 224Z | | | | IX | 0-0 | 34-45-13 | D04597P | DED | | | D04591J | | | 29 | 153-154, 157, 167-199, 277-278 |
| 306 | 20 | | UA | | 1-6 | 31-51-31 | D04597P | | | | MF | GD00301 | S.. | 2 | 050-099 |
| 306 | 20 | | UA | | 3-0 | 31-51-31 | D04597P | | | | MF | GD00301 | S.. | 2 | 150-199, 275-299 |
| 306B | 24 | | PX | MF | 41-0 | 31-51-31 | D04597P | | | 12 | | D00697 | | 5 | ALL |
| 306R | 24 | | PX | MF | 0-0 | 31-51-31 | D04597P | | | 13 | | D00697 | | 3 | ALL |
| 306Y | 24 | | PX | MF | 0-0 | 31-51-31 | D04597P | | | | MF | D00697 | | 6 | ALL |
| 306Z | | | | MF | 0-0 | 31-51-31 | D04597P | | | | MF | D00697 | DED | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0450
Page 14 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0460 | 286T0460 | | | L WING REAR SPAR-R1-BST PUMP | | | | | | | | | | | | | |
| 001 | 18 | | UA | | 9-2 | 28-22-11 | D01550 | | 3 | | | | GD03520 | S.. | N | | ALL |
| 002 | 20 | | VF | B | 19-6 | 28-42-11 | D01538 | | 3 | | | | D04600P | | 1 | | ALL |
| 002Z | | | | B | 0-0 | 28-42-11 | GD04124 | | S.. | N | * | | GD04050 | S.. | N | *1 | 050-099, 155-199, 276-299 |
| 002Z | | | | B | 0-0 | 28-42-11 | GD04124 | | S.. | N | * | | GD04050 | S.. | N | | 150-154, 275 |
| 003 | 18 | | UA | | 2-9 | 28-42-11 | D01538 | | 2 | DK | | | GD03362 | D.. | N | | ALL |
| 004 | 18 | | UA | | 1-5 | 28-42-11 | D01538 | | 4 | DK | | | GD04124 | S.. | N | | ALL |
| 005 | 20 | | VF | C | 15-6 | 28-42-12 | D02806 | | 3 | | | | D04600P | | 5 | | ALL |
| 005Z | | | | C | 0-0 | 28-42-12 | GD04110 | | S.. | N | * | | GD04050 | S.. | N | *1 | 050-099, 155-199, 276-299 |
| 005Z | | | | C | 0-0 | 28-42-12 | GD04110 | | S.. | N | * | | GD04050 | S.. | N | | 150-154, 275 |
| 006 | 18 | | UA | | 2-8 | 28-42-12 | D02806 | | 2 | DK | | | GD03366 | D.. | N | | ALL |
| 007 | 18 | | UA | | 1-5 | 28-42-12 | D02806 | | 4 | DK | | | GD04110 | S.. | N | | ALL |
| 008 | 20 | | VF | F | 14-8 | 28-42-31 | D02806 | | 1 | | | | SM00001 | | 9 | | ALL |
| 008Z | | | | F | 0-0 | 28-42-31 | GD04110 | | S.. | N | * | | SM00002 | | 9 | | ALL |
| 009 | 20 | | VF | D | 18-8 | 28-42-31 | D01538 | | 1 | | | | SM00001 | | 9 | | ALL |
| 009Z | | | | D | 0-0 | 28-42-31 | GD04124 | | S.. | N | * | | SM00002 | | 9 | | ALL |
| 010 | 20 | | VF | E | 1-0 | 28-42-31 | D04600P | | 6 | | | | SM00001 | | 9 | | ALL |
| 010Z | | | | E | 0-0 | 28-42-31 | GD04050 | | S.. | N | *2 | | SM00002 | | 9 | | 050-099, 155-199, 276-299 |
| 010Z | | | | E | 0-0 | 28-42-31 | GD04050 | | S.. | N | | | SM00002 | | 9 | | 150-154, 275 |
| 100 | 18 | | VF | DY | 15-0 | 28-22-31 | D04600P | | 9 | | | | D20058 | | 5 | | ALL |
| 100Z | | | | DY | 0-0 | 28-22-31 | D04600P | | DED | | | | D20058 | DED | | | ALL |
| 101 | 18 | | VF | EA | 15-0 | 28-22-31 | D04600P | | 10 | | | | D20058 | | 4 | | ALL |
| 101Z | | | | EA | 0-0 | 28-22-31 | D04600P | | DED | | | | D20058 | DED | | | ALL |
| 102 | 18 | | VF | EB | 15-0 | 28-22-31 | D04600P | | 11 | | | | D20058 | | 2 | | ALL |
| 102Z | | | | EB | 0-0 | 28-22-31 | D04600P | | DED | | | | D20058 | DED | | | ALL |
| 103 | 18 | | VF | EC | 15-0 | 28-22-31 | D04600P | | 12 | | | | D20058 | | 3 | | ALL |
| 103Z | | | | EC | 0-0 | 28-22-31 | D04600P | | DED | | | | D20058 | DED | | | ALL |
| 104 | 18 | | VF | ED | 15-0 | 28-22-31 | GD04050 | | S.. | N | *2 | | D20058 | | 7 | | ALL |
| 104Z | | | | ED | 0-0 | 28-22-31 | GD04050 | | DED | | | | D20058 | DED | | | ALL |
| 301B | 18 | | VH | A | 26-7 | 28-22-11 | D01550 | | 2 | | | | D04600P | | 2 | | ALL |
| 301R | 18 | | VH | A | 0-0 | 28-22-11 | D01550 | | 4 | | | | D04600P | | 3 | | ALL |
| 301Y | 18 | | VH | A | 0-0 | 28-22-11 | D01550 | | 6 | | | | D04600P | | 4 | | ALL |
| 301Z | | | | A | 0-0 | 28-22-11 | GD04048 | | S.. | N | | | GD04050 | S.. | N | *2 | ALL |
| W0461 | 286T0461 | | | AFCS MODE CONT C,SHELF TO CONT PNL | | | | | | | | | | | | | |
| 001 | 22 | | PA | | 26-0 | 22-11-32 | D04593J | | 1 | | | | D04501J | | 1 | | ALL |
| 002 | 22 | | PA | | 26-0 | 22-11-32 | D04593J | | 2 | | | | D04501J | | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0460

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0461 | 286T0461 | | | AFCS MODE CONT C,SHELF TO CONT PNL (continued) | | | | | | | | | | | |
| 009 | 22 | | PA | | 26-0 | SPARE | D04593J | 7 | | | D04501J | 7 | | | ALL |
| 201B | 24 | | PW | IA | 26-0 | 22-12-31 | D04593J | 4 | | | D04501J | 4 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 22-12-31 | D04593J | 3 | | | D04501J | 3 | | | ALL |
| 201Z | | | | IA | 0-0 | 22-12-31 | D04593J | 5 | | | D04501J | 5 | | | ALL |
| W0462 | 286T0462 | | | R WING REAR SPAR-S2B-FUEL | | | | | | | | | | | |
| 004 | 18 | | VF | B | 20-2 | 28-22-21 | SP01752 | | 9 | | SP00466 | | 9 | | ALL |
| 004Z | | | | B | 0-0 | 28-22-21 | SP01942 | | 9 | | SP01944 | | 9 | | ALL |
| 010 | 18 | | UA | | 1-5 | 28-21-13 | GD03418 | D.. | N | | D02800 | 1 | DK | | ALL |
| 011 | 18 | | UA | | 1-5 | 28-21-13 | GD03418 | D.. | N | | D02800 | 4 | DK | | ALL |
| 012 | 18 | | UA | | 1-9 | 28-21-13 | GD03420 | S.. | N | | D02800 | 3 | DK | | ALL |
| 020 | 20 | | VF | AT | 3-1 | 31-31-22 | D04652P | | 12 | | D01921 | | 1 | | ALL |
| 020Z | | | | AT | 0-0 | 31-31-22 | D04652P | DED | | | D01921 | DED | | | ALL |
| 021 | 20 | | UA | | 1-4 | 31-31-22 | D04652P | REF | | FA | GD04162 | S.. | N | | ALL |
| 201B | 20 | | VG | A | 18-3 | 28-21-13 | D04652P | | 7 | | D02800 | | 2 | | ALL |
| 201R | 20 | | VG | A | 0-0 | 28-21-13 | D04652P | | 6 | | D02800 | | 5 | | ALL |
| 201Z | | | | A | 0-0 | 28-21-13 | GD04162 | S.. | N | | GD04028 | S.. | N | | ALL |
| 202B | 20 | | VG | IB | 3-1 | 31-31-22 | D04652P | | 11 | | D01921 | | 3 | | 050-099, 162-199, 275-299 |
| 202B | 20 | | VG | IB | 3-1 | 31-31-22 | D01921 | | 3 | | D04652P | | 11 | | 150-157 |
| 202R | 20 | | VG | IB | 0-0 | 31-31-22 | D04652P | | 10 | | D01921 | | 2 | | 050-099, 162-199, 275-299 |
| 202R | 20 | | VG | IB | 0-0 | 31-31-22 | D01921 | | 2 | | D04652P | | 10 | | 150-157 |
| 202Z | | | | IB | 0-0 | 31-31-22 | D04652P | REF | | FA | D01921 | DED | | | 050-099, 162-199, 275-299 |
| 202Z | | | | IB | 0-0 | 31-31-22 | D01921 | DED | | | D04652P | REF | | FA | 150-157 |
| FRA | | | | | 0-0 | 31-31-22 | D04652P | REF | | FA | D04652P | | 8 | | ALL |
| W0463 | 286T0463 | | | AFCS MODE CONT R,SHELF AND PNL TO CONT PNL | | | | | | | | | | | |
| 001 | 22 | | PA | | 34-0 | 22-11-22 | D04595J | | 1 | | D05423J | | 1 | | ALL |
| 002 | 22 | | PA | | 34-0 | 22-11-22 | D04595J | | 2 | | D05423J | | 2 | | ALL |
| 003 | 22 | | PA | | 34-0 | 22-11-22 | D04595J | | 3 | | D05423J | | 3 | | ALL |
| 009 | 22 | | PA | | 34-0 | SPARE | D05423J | | 13 | | D04595J | | 13 | | ALL |
| 010 | 22 | | PA | | 34-0 | SPARE | D05423J | | 16 | | D04595J | | 16 | | ALL |
| 011 | 22 | | PA | | 34-0 | SPARE | D05423J | | 17 | | D04595J | | 17 | | ALL |
| 201B | 24 | | PW | IA | 34-0 | 22-12-21 | D04595J | | 5 | | D05423J | | 5 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 22-12-21 | D04595J | | 4 | | D05423J | | 4 | | ALL |
| 201Z | | | | IA | 0-0 | 22-12-21 | D04595J | | 6 | | D05423J | | 6 | | ALL |
| 202B | 24 | | PW | IB | 34-0 | 22-13-21 | D04595J | | 8 | | D05423J | | 8 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0460

Page 2

Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | Effectivity | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|-------------|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | | Splice |
| W0463 | 286T0463 | | | AFCS MODE CONT R,SHELF AND PNL TO CONT PNL (continued) | | | | | | | | | | | |
| 202R | 24 | PW | IB | 0-0 | 22-13-21 | D04595J | | 7 | | | D05423J | | 7 | | ALL |
| 202Z | | | IB | 0-0 | 22-13-21 | D04595J | | 9 | | | D05423J | | 9 | | ALL |
| 203B | 24 | PW | IC | 34-0 | 22-14-21 | D04595J | | 11 | | | D05423J | | 11 | | ALL |
| 203R | 24 | PW | IC | 0-0 | 22-14-21 | D04595J | | 10 | | | D05423J | | 10 | | ALL |
| 203Z | | | IC | 0-0 | 22-14-21 | D04595J | | 12 | | | D05423J | | 12 | | ALL |
| W0464 | 286T0464 | | | R WING REAR SPAR-L2-FLT CONT/FUEL | | | | | | | | | | | |
| 011 | 20 | VF | N | 17-2 | 28-42-11 | D04272P | | 12 | | | D02822 | | 3 | | ALL |
| 011Z | | | N | 0-0 | 28-42-11 | GD03962 | | S.. | N | | GD04120 | | S.. | N | 050-099, 150-154, 162-165, 275-276 |
| 011Z | | | N | 0-0 | 28-42-11 | GD03962 | | S.. | N | | GD03436 | | S.. | N | 155-157, 166-199, 277-299 |
| 012 | 18 | UA | | 3-6 | 28-42-11 | GD03342 | | D.. | N | | D02822 | | 2 | DK | ALL |
| 013 | 18 | UA | | 3-5 | 28-42-11 | GD03344 | | S.. | N | | D02822 | | 4 | DK | ALL |
| 018 | 18 | UA | | 1-3 | 27-51-41 | GD03476 | | S.. | N | | D01632 | | 10 | | ALL |
| 020 | 18 | UA | | 2-4 | 27-62-11 | GD03478 | | D.. | N | | D02266 | | 2 | | ALL |
| 025 | 20 | VF | P | 14-10 | 28-42-12 | D04272P | | 13 | | | D02808 | | 3 | | ALL |
| 025Z | | | P | 0-0 | 28-42-12 | GD03960 | | S.. | N | | GD04108 | | S.. | N | ALL |
| 026 | 18 | UA | | 2-6 | 28-42-12 | GD03328 | | D.. | N | | D02808 | | 2 | DK | ALL |
| 027 | 18 | UA | | 2-5 | 28-42-12 | GD03330 | | S.. | N | | D02808 | | 4 | DK | ALL |
| 201B | 20 | VG | A | 60-3 | 27-51-41 | D04416P | | 1 | | | D01632 | | 8 | | ALL |
| 201R | 20 | VG | A | 0-0 | 27-51-41 | D04416P | | 2 | | | D01632 | | 9 | | ALL |
| 201Z | | | A | 0-0 | 27-51-41 | GD03970 | | S.. | N | | GD03476 | | S.. | N | ALL |
| 204B | 20 | VG | G | 20-11 | 27-62-11 | D04272P | | 7 | | | D02266 | | 3 | | ALL |
| 204R | 20 | VG | G | 0-0 | 27-62-11 | D04272P | | 11 | | | D02266 | | 1 | | ALL |
| 204Z | | | G | 0-0 | 27-62-11 | GD03960 | | S.. | N | | GD04022 | | S.. | N | ALL |
| 205B | 20 | VG | IE | 88-3 | 27-18-11 | D01640 | | 1 | | | D04272P | | 21 | | 155-157, 166-199, 277-299 |
| 205R | 20 | VG | IE | 0-0 | 27-18-11 | D01640 | | 2 | | | D04272P | | 4 | | 155-157, 166-199, 277-299 |
| 205Z | | | IE | 0-0 | 27-18-11 | GD03948 | | S.. | N | | GD03960 | | S.. | N | 155-157, 166-199, 277-299 |
| 206B | 20 | VG | IF | 37-0 | 27-18-11 | D01588 | | 1 | | | D04272P | | 23 | | 155-157, 166-199, 277-299 |
| 206R | 20 | VG | IF | 0-0 | 27-18-11 | D01588 | | 2 | | | D04272P | | 1 | | 155-157, 166-199, 277-299 |
| 206Z | | | IF | 0-0 | 27-18-11 | GD03950 | | S.. | N | | GD03960 | | S.. | N | 155-157, 166-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0460

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------|--|---------|-------|------|------|--------|---------|------|------|--------|------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0464 | 286T0464 | | | | R WING REAR SPAR-L2-FLT CONT/FUEL (continued) | | | | | | | | | | | |
| 304B | 20 | VH | MD | 90-0 | 27-18-11 | D01640 | | 4 | | | SP02632 | | 9 | | 155-157, 166-199, 277-299 | |
| 304R | 20 | VH | MD | 0-0 | 27-18-11 | D01640 | | 3 | | | SP05086 | | 9 | | 155-157, 166-199, 277-299 | |
| 304Y | 20 | VH | MD | 0-0 | 27-18-11 | D01640 | | 5 | | | SP02636 | | 9 | | 155-157, 166-199, 277-299 | |
| 304Z | | | MD | 0-0 | 27-18-11 | GD03948 | | S.. | N | | GD03962 | | S.. | N | 155-157, 166-199, 277-299 | |
| 305B | 20 | VH | ME | 37-1 | 27-18-11 | D01588 | | 4 | | | D06978P | | 2 | | 155-157, 166-199, 277-299 | |
| 305R | 20 | VH | ME | 0-0 | 27-18-11 | D01588 | | 3 | | | D06978P | | 1 | | 155-157, 166-199, 277-299 | |
| 305Y | 20 | VH | ME | 0-0 | 27-18-11 | D01588 | | 5 | | | D06978P | | 3 | | 155-157, 166-199, 277-299 | |
| 305Z | | | ME | 0-0 | 27-18-11 | GD03950 | | S.. | N | | GD03962 | | S.. | N | 155-157, 166-199, 277-299 | |
| 401B | 20 | U4 | D | 60-3 | 27-51-41 | D04416P | | 3 | | | D01632 | | 4 | | ALL | |
| 401G | 20 | U4 | D | 0-0 | 27-51-41 | D04416P | | 6 | | | D01632 | | 7 | | ALL | |
| 401R | 20 | U4 | D | 0-0 | 27-51-41 | D04416P | | 4 | | | D01632 | | 5 | | ALL | |
| 401Y | 20 | U4 | D | 0-0 | 27-51-41 | D04416P | | 5 | | | D01632 | | 6 | | ALL | |
| 401Z | | | D | 0-0 | 27-51-41 | GD04004 | | S.. | N | | GD03476 | | S.. | N | ALL | |
| 404B | 20 | U4 | K | 95-0 | 27-18-11 | SP02632 | | 9 | | | D01640 | | 4 | | 050-099, 162-165, 276 | |
| 404B | 20 | U4 | K | 93-0 | 27-18-11 | SP02632 | | 9 | | | D01640 | | 4 | | 150-154, 275 | |
| 404G | 20 | U4 | K | 0-0 | 27-18-11 | D04272P | | 21 | | | D01640 | | 1 | | 050-099, 150-154, 162-165, 275-276 | |
| 404R | 20 | U4 | K | 0-0 | 27-18-11 | D04272P | | 4 | | | D01640 | | 2 | | 050-099, 150-154, 162-165, 275-276 | |
| 404Y | 20 | U4 | K | 0-0 | 27-18-11 | SP02636 | | 9 | | | D01640 | | 5 | | 050-099, 150-154, 162-165, 275-276 | |
| 404Z | | | K | 0-0 | 27-18-11 | GD03962 | | S.. | N | | GD03948 | | S.. | N | 050-099, 150-154, 162-165, 275-276 | |
| 405B | 20 | U4 | L | 37-0 | 27-18-11 | D04272P | | 1 | | | D01588 | | 2 | | 050-099, 150-154, 162-165, 275-276 | |
| 405G | 20 | U4 | L | 0-0 | 27-18-11 | D04272P | | 23 | | | D01588 | | 1 | | 050-099, 150-154, 162-165, 275-276 | |
| 405R | 20 | U4 | L | 0-0 | 27-18-11 | D04272P | | 2 | | | D01588 | | 5 | | 050-099, 150-154, 162-165, 275-276 | |
| 405Y | 20 | U4 | L | 0-0 | 27-18-11 | D04272P | | 3 | | | D01588 | | 4 | | 050-099, 150-154, 162-165, 275-276 | |

WIRE LIST
D280T132

91-21-11
Section W0460
Page 4
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0464 | 286T0464 | | | R WING REAR SPAR-L2-FLT CONT/FUEL (continued) | | | | | | | | | | | | | |
| 405Z | | | | L | 0-0 | 27-18-11 | GD03960 | S.. | N | | | | GD03950 | S.. | N | | 050-099, 150-154, 162-165, 275-276 |
| 406B | 20 | U4 | M | | 60-1 | 27-58-11 | D04272P | | 24 | | | | D01632 | | 3 | | ALL |
| 406G | 20 | U4 | M | | 0-0 | 27-58-11 | D04272P | | 10 | | | | D01632 | | 11 | | ALL |
| 406R | 20 | U4 | M | | 0-0 | 27-58-11 | D04272P | | 9 | | | | D01632 | | 2 | | ALL |
| 406Y | 20 | U4 | M | | 0-0 | 27-58-11 | D04272P | | 8 | | | | D01632 | | 1 | | ALL |
| 406Z | | | | M | 0-0 | 27-58-11 | GD03970 | S.. | N | | | | GD03476 | S.. | N | | ALL |
| A-A | | | | | 0-0 | 27-18-11 | M01148 | | A | | | | SP02632 | | 9 | | ALL |
| A-B | | | | | 0-0 | 27-18-11 | M01149 | | A | | | | SP02636 | | 9 | | ALL |
| W0465 | 286T0465 | | | FCC L,SHELF TO XDCR'S | | | | | | | | | | | | | |
| 006Y | 22 | PJ | | | 29-0 | 27-41-11 | D04337J | | 21 | | | | SP00011 | | 9 | | 150-199 |
| 007 | 22 | PA | | | 28-0 | 31-31-25 | D00133 | | 2 | | | | D04337J | 22 | | | 050-099, 150-199 |
| 008 | 20 | PA | | | 10-0 | 31-31-25 | D00133 | | 1 | | | | GD00641 | S.. | 2 | | 050-099, 150-199 |
| 009 | 20 | PA | | | 10-0 | 31-31-25 | D00133 | | 5 | | | | GD00641 | S.. | 2 | | 050-099, 150-199 |
| 010 | 22 | PA | | | 26-0 | 31-31-25 | D00135 | | 2 | | | | D04337J | 25 | | | 050-099, 150-199 |
| 011 | 20 | PA | | | 3-0 | 31-31-25 | D00135 | | 1 | | | | GD00641 | S.. | 2 | | 050-099, 150-199 |
| 012 | 20 | PA | | | 3-0 | 31-31-25 | D00135 | | 5 | | | | GD00641 | S.. | 2 | | 050-099, 150-199 |
| 013 | 22 | PA | | | 19-0 | 31-31-25 | D00137 | | 2 | | | | D04337J | 28 | | | 050-099, 150-199 |
| 014 | 20 | PA | | | 9-0 | 31-31-25 | D00137 | | 1 | | | | GD00657 | S.. | E | | 050-099, 150-199 |
| 015 | 20 | PA | | | 9-0 | 31-31-25 | D00137 | | 5 | | | | GD00657 | S.. | E | | 050-099, 150-199 |
| 016Y | 22 | PJ | | | 23-0 | 27-41-11 | SP00009 | | 9 | | | | SP00567 | | 9 | | 150-166 |
| 016Y | 22 | PJ | | | 18-0 | 27-41-11 | SP00009 | | 9 | | | | SP00567 | | 9 | | 167-199 |
| 017Y | 22 | PJ | | | 23-0 | 27-41-11 | SP00011 | | 9 | | | | SP00565 | | 9 | | 150-166 |
| 017Y | 22 | PJ | | | 18-0 | 27-41-11 | SP00011 | | 9 | | | | SP00565 | | 9 | | 167-199 |
| 018Y | 22 | PJ | | | 23-0 | 27-41-11 | SP00027 | | 9 | | | | SP00571 | | 9 | | 150-166 |
| 018Y | 22 | PJ | | | 18-0 | 27-41-11 | SP00027 | | 9 | | | | SP00571 | | 9 | | 167-199 |
| 019Y | 22 | PJ | | | 23-0 | 27-41-11 | SP00015 | | 9 | | | | SP00569 | | 9 | | 150-166 |
| 019Y | 22 | PJ | | | 18-0 | 27-41-11 | SP00015 | | 9 | | | | SP00569 | | 9 | | 167-199 |
| 204B | 22 | PB | ID | | 28-0 | 31-31-25 | D00133 | | 9 | | | | D04337J | 24 | | | 050-099, 150-199 |
| 204R | 22 | PB | ID | | 0-0 | 31-31-25 | D00133 | | 10 | | | | D04337J | 23 | | | 050-099, 150-199 |
| 205B | 22 | PB | IE | | 26-0 | 31-31-25 | D00135 | | 9 | | | | D04337J | 27 | | | 050-099, 150-199 |
| 205R | 22 | PB | IE | | 0-0 | 31-31-25 | D00135 | | 10 | | | | D04337J | 26 | | | 050-099, 150-199 |
| 206B | 22 | PB | IF | | 19-0 | 31-31-25 | D00137 | | 9 | | | | D04337J | 30 | | | 050-099, 150-199 |
| 206R | 22 | PB | IF | | 0-0 | 31-31-25 | D00137 | | 10 | | | | D04337J | 29 | | | 050-099, 150-199 |
| A-A | | | | | 0-0 | 27-41-11 | S00334 | | COM | E | | | SP00009 | | 9 | | 150-166 |
| A-A | | | | | 0-0 | 27-41-11 | S00334 | | COM | | | | SP00009 | | 9 | | 167-199 |
| A-C | | | | | 0-0 | 27-41-11 | S00334 | | NO | E | | | SP00011 | | 9 | | 150-166 |
| A-C | | | | | 0-0 | 27-41-11 | S00334 | | NO | | | | SP00011 | | 9 | | 167-199 |

WIRE LIST

D280T132

91-21-11

Section W0460

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0465 | 286T0465 | | | FCC L,SHELF TO XDCR'S (continued) | | | | | | | | | | | |
| B-A | | | | | 0-0 | 27-41-11 | S00335 | COM | E | | SP00027 | | 9 | | 150-166 |
| B-A | | | | | 0-0 | 27-41-11 | S00335 | COM | | | SP00027 | | 9 | | 167-199 |
| B-C | | | | | 0-0 | 27-41-11 | S00335 | NO | E | | SP00015 | | 9 | | 150-166 |
| B-C | | | | | 0-0 | 27-41-11 | S00335 | NO | | | SP00015 | | 9 | | 167-199 |
| D-A | | | | | 0-0 | 27-41-21 | S00838 | COM | E | | SP00575 | | 9 | | 150-166 |
| D-A | | | | | 0-0 | 27-41-21 | S00838 | COM | | | SP00575 | | 9 | | 167-199 |
| D-C | | | | | 0-0 | 27-41-21 | S00838 | NO | E | | SP00573 | | 9 | | 150-166 |
| D-C | | | | | 0-0 | 27-41-21 | S00838 | NO | | | SP00573 | | 9 | | 167-199 |
| E-A | | | | | 0-0 | 27-41-21 | S00839 | COM | E | | SP00579 | | 9 | | 150-166 |
| E-A | | | | | 0-0 | 27-41-21 | S00839 | COM | | | SP00579 | | 9 | | 167-199 |
| E-C | | | | | 0-0 | 27-41-21 | S00839 | NO | E | | SP00577 | | 9 | | 150-166 |
| E-C | | | | | 0-0 | 27-41-21 | S00839 | NO | | | SP00577 | | 9 | | 167-199 |
| W0466 | 286T0466 | | | L WING INBD FS-R1-FLT CONT | | | | | | | | | | | |
| 001 | 18 | | UA | | 9-10 | 27-81-21 | D04420P | | | 1 | D01522 | | 1 | | ALL |
| 002 | 18 | | UA | | 9-10 | 27-81-21 | D04420P | | | 2 | D01522 | | 2 | | ALL |
| 003 | 18 | | UA | | 9-10 | 27-81-21 | D04420P | | | 3 | D01522 | | 3 | | ALL |
| 004 | 18 | | UA | | 9-10 | 27-81-21 | D04420P | | | 4 | D01522 | | 7 | | ALL |
| 005 | 18 | | UA | | 3-0 | 27-81-21 | D01522 | | | 6 | GD03430 | D.. | N | | ALL |
| 006 | 18 | | UA | | 2-8 | 27-81-21 | D01522 | | | 5 | GD03432 | A.. | N | | ALL |
| 007 | 18 | | UA | | 2-5 | 27-81-21 | D01522 | | | 8 | GD03434 | S.. | N | | ALL |
| W0468 | 286T0468 | | | L WING OUTBD FS-R2-LIGHTING | | | | | | | | | | | |
| 001 | 18 | | UA | | 1-0 | 33-43-11 | D04438J | | | 4 | SM00001 | | 9 | | ALL |
| 003 | 18 | | UA | | 1-3 | 33-44-21 | D02752 | | | 3 | GD01650 | S.. | N | | ALL |
| 004 | 18 | | VF | M | 5-2 | 30-11-11 | D02388 | | | 2 | GD01656 | D.. | N | | ALL |
| 004Z | | | | M | 0-0 | 30-11-11 | GD03648 | | | S.. | N | | N | | ALL |
| 005 | 18 | | VF | P | 5-2 | 30-11-11 | D02388 | | | 3 | D04438J | | 1 | | ALL |
| 005Z | | | | P | 0-0 | 30-11-11 | GD03648 | | | S.. | N | | N | | ALL |
| 006 | 18 | | UA | | 1-6 | 30-11-11 | D02388 | | | 4 | GD03648 | S.. | N | | ALL |
| 100 | 12 | | UA | | 1-0 | 33-43-11 | D02074 | | | 3 | SM00004 | | 9 | | 050-099, 155-199, 276-299 |
| 201B | 12 | | UB | A | 1-0 | 33-43-11 | D02074 | | | 2 | SM00003 | | 9 | | 150-154, 275 |
| 201R | 12 | | UB | A | 0-0 | 33-43-11 | D02074 | | | 3 | SM00004 | | 9 | | 150-154, 275 |
| 202B | 12 | | UB | B | 1-5 | 33-43-11 | D02074 | | | 7 | SM00005 | | 9 | | ALL |
| 202R | 12 | | UB | B | 0-0 | 33-43-11 | D02074 | | | 5 | GD01640 | S.. | N | | ALL |
| 203B | 12 | | VG | C | 2-8 | 33-43-11 | D04430J | | | 1 | SM00008 | | 9 | | ALL |
| 203R | 12 | | VG | C | 0-0 | 33-43-11 | D04430J | | | 2 | SM00004 | | 9 | | ALL |
| 203Z | | | | C | 0-0 | 33-43-11 | GD03848 | | | S.. | N | | N | *1 | ALL |

WIRE LIST
D280T132

91-21-11
Section W0460
Page 6
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0468 | 286T0468 | | | L WING OUTBD FS-R2-LIGHTING (continued) | | | | | | | | | | | | | |
| 204B | 12 | VG | D | 4-1 | 33-43-11 | D04432J | | 1 | | | | | SM00005 | | 9 | | ALL |
| 204R | 12 | VG | D | 0-0 | 33-43-11 | D04432J | | 2 | | | | | SM00007 | | 9 | | ALL |
| 204Z | | | D | 0-0 | 33-43-11 | GD01652 | | S.. | N | | | | GD01638 | S.. | N | *2 | ALL |
| 205B | 12 | VG | E | 68-1 | 33-43-11 | D02074 | | 2 | | | | | SM00001 | | 9 | | 050-099, 155-199, 276-299 |
| 205B | 12 | VG | E | 68-1 | 33-43-11 | SM00003 | | | 9 | | | | SM00001 | | 9 | | 150-154, 275 |
| 205R | 12 | VG | E | 0-0 | 33-43-11 | SM00004 | | | 9 | | | | GD01636 | A.. | N | | ALL |
| 205Z | | | E | 0-0 | 33-43-11 | GD01638 | | S.. | N | | | | GD03644 | S.. | N | *1 | ALL |
| 206 | 12 | UA | | 1-0 | 33-43-11 | D02074 | | 1 | | | | | SM00007 | | 9 | | ALL |
| 207 | 12 | UA | | 1-0 | 33-43-11 | D02074 | | 8 | | | | | SM00008 | | 9 | | ALL |
| 208B | 12 | VG | J | 4-1 | 33-43-11 | D04432J | | 3 | | | | | SM00008 | | 9 | | ALL |
| 208R | 12 | VG | J | 0-0 | 33-43-11 | D04432J | | 4 | | | | | SM00007 | | 9 | | ALL |
| 208Z | | | J | 0-0 | 33-43-11 | GD01652 | | S.. | N | | | | GD01638 | S.. | N | *1 | ALL |
| 209B | 12 | VG | K | 2-8 | 33-43-11 | D04430J | | 3 | | | | | SM00005 | | 9 | | ALL |
| 209R | 12 | VG | K | 0-0 | 33-43-11 | D04430J | | 4 | | | | | SM00004 | | 9 | | ALL |
| 209Z | | | K | 0-0 | 33-43-11 | GD03848 | | S.. | N | | | | GD01638 | S.. | N | *2 | ALL |
| 210 | 12 | VF | L | 68-1 | 33-43-11 | SM00007 | | | 9 | | | | GD01636 | A.. | N | | ALL |
| 210Z | | | L | 0-0 | 33-43-11 | GD01638 | | S.. | N | | | | GD03644 | S.. | N | *1 | ALL |
| 211B | 18 | VG | N | 66-3 | 33-44-21 | D02752 | | 1 | | | | | D04438J | | 6 | | ALL |
| 211R | 18 | VG | N | 0-0 | 33-44-21 | D02752 | | 2 | | | | | GD01636 | A.. | N | | ALL |
| 211Z | | | N | 0-0 | 33-44-21 | GD01650 | | S.. | N | | | | GD03644 | S.. | N | | 050-099, 150-154 |
| 211Z | | | N | 0-0 | 33-44-21 | GD01650 | | S.. | N | | | | GD03644 | S.. | N | *2 | 155-199, 275-299 |
| 213B | 18 | VG | S | 5-3 | SPARE | D02384 | | CAP | Y | | | | D04438J | | 2 | | 155-199 |
| 213B | 18 | VG | S | 5-3 | 30-11-11 | D02384 | | 1 | DK | | | | D04438J | | 2 | | 275-299 |
| 213R | 18 | VG | S | 0-0 | SPARE | D02384 | | CAP | Y | | | | D04438J | | 3 | | 155-199 |
| 213R | 18 | VG | S | 0-0 | 30-11-11 | D02384 | | 2 | DK | | | | D04438J | | 3 | | 275-299 |
| 213Z | | | S | 0-0 | SPARE | GD03648 | | S.. | N | | | | GD03644 | S.. | N | *2 | 155-199, 275-299 |
| W0469 | 286T0469 | | | FCC R,SHELF TO XDCR'S | | | | | | | | | | | | | |
| 004Y | 22 | PJ | | 37-0 | 27-41-21 | D04345J | | 2 | | | | | SP00109 | | 9 | | 050-099 |
| 006Y | 22 | PJ | | 37-0 | 27-41-21 | D04345J | | 1 | | | | | SP00033 | | 9 | | ALL |
| 007 | 20 | PA | | 33-0 | 27-32-21 | D04345J | | 3 | | | | | D01399 | A | \$D | | ALL |
| 008 | 20 | PA | | 33-0 | 27-32-21 | D04345J | | 4 | | | | | D01399 | B | \$D | | ALL |
| 016Y | 22 | PJ | | 23-0 | 27-41-21 | SP00031 | | | 9 | | | | SP00575 | | 9 | | 050-099, 150-199, 278-299 |
| 017Y | 22 | PJ | | 23-0 | 27-41-21 | SP00033 | | | 9 | | | | SP00573 | | 9 | | 050-099, 150-199, 278-299 |
| 018Y | 22 | PJ | | 23-0 | 27-41-21 | SP00107 | | | 9 | | | | SP00579 | | 9 | | 050-099, 150-199, 278-299 |

WIRE LIST

D280T132

91-21-11

Section W0460

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0469 | 286T0469 | | | FCC R,SHELF TO XDCR'S (continued) | | | | | | | | | | | |
| 019Y | 22 | | PJ | | 23-0 | 27-41-21 | SP00105 | | | | 9 | | | | 050-099, 150-199, 278-299 |
| A-A | | | | | 0-0 | 27-41-21 | S00337 | COM | E | | SP00031 | | | | 050-099, 150-166 |
| A-A | | | | | 0-0 | 27-41-21 | S00337 | COM | | | SP00031 | | | | 167-199, 275-299 |
| A-C | | | | | 0-0 | 27-41-21 | S00337 | NO | E | | SP00033 | | | | 050-099, 150-166 |
| A-C | | | | | 0-0 | 27-41-21 | S00337 | NO | | | SP00033 | | | | 167-199, 275-299 |
| B-A | | | | | 0-0 | 27-41-21 | S00338 | COM | E | | SP00107 | | | | 050-099, 150-166 |
| B-A | | | | | 0-0 | 27-41-21 | S00338 | COM | | | SP00107 | | | | 167-199, 275-299 |
| B-C | | | | | 0-0 | 27-41-21 | S00338 | NO | E | | SP00105 | | | | 050-099, 150-166 |
| B-C | | | | | 0-0 | 27-41-21 | S00338 | NO | | | SP00105 | | | | 167-199, 275-299 |
| C-A | | | | | 0-0 | 27-41-21 | S00339 | COM | E | | SP00107 | | | | 050-099 |
| C-C | | | | | 0-0 | 27-41-21 | S00339 | NO | | | SP00109 | | | | 050-099 |
| D-A | | | | | 0-0 | 27-41-11 | S00836 | COM | E | | SP00567 | | | | 050-099, 150-166 |
| D-A | | | | | 0-0 | 27-41-11 | S00836 | COM | | | SP00567 | | | | 167-199, 278-299 |
| D-C | | | | | 0-0 | 27-41-11 | S00836 | NO | E | | SP00565 | | | | 050-099, 150-166 |
| D-C | | | | | 0-0 | 27-41-11 | S00836 | NO | | | SP00565 | | | | 167-199, 278-299 |
| E-A | | | | | 0-0 | 27-41-11 | S00837 | COM | E | | SP00571 | | | | 050-099, 150-166 |
| E-A | | | | | 0-0 | 27-41-11 | S00837 | COM | | | SP00571 | | | | 167-199, 278-299 |
| E-C | | | | | 0-0 | 27-41-11 | S00837 | NO | E | | SP00569 | | | | 050-099, 150-166 |
| E-C | | | | | 0-0 | 27-41-11 | S00837 | NO | | | SP00569 | | | | 167-199, 278-299 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0470 | 286T0470 | | | R WING OUTBD FS-R2-LIGHTING | | | | | | | | | | | | | |
| 001 | 18 | | UA | | 0-10 | 33-43-11 | D04380J | | 4 | | | | SM00001 | | 9 | | ALL |
| 003 | 18 | | UA | | 1-4 | 33-44-21 | D03466 | | 3 | | | | GD03714 | S.. | N | | ALL |
| 004 | 18 | | VF | M | 5-2 | 30-11-11 | D02386 | | 2 | DK | | | GD01658 | D.. | N | | ALL |
| 004Z | | | | M | 0-0 | 30-11-11 | GD03732 | | S.. | N | | | GD03718 | S.. | N | | ALL |
| 005 | 18 | | VF | P | 5-0 | 30-11-11 | D02386 | | 3 | DK | | | D04380J | | 1 | | ALL |
| 005Z | | | | P | 0-0 | 30-11-11 | GD03732 | | S.. | N | | | GD03718 | S.. | N | | ALL |
| 006 | 18 | | UA | | 1-7 | 30-11-11 | D02386 | | 4 | DK | | | GD03732 | S.. | N | | ALL |
| 100 | 12 | | UA | | 1-0 | 33-43-11 | D02070 | | 3 | | | | SM00004 | | 9 | | 050-099, 155-199, 276-299 |
| 201B | 12 | | UB | A | 1-0 | 33-43-11 | D02070 | | 2 | | | | SM00003 | | 9 | | 150-154, 275 |
| 201R | 12 | | UB | A | 0-0 | 33-43-11 | D02070 | | 3 | | | | SM00004 | | 9 | | 150-154, 275 |
| 202B | 12 | | UB | B | 1-6 | 33-43-11 | D02070 | | 8 | | | | SM00005 | | 9 | | ALL |
| 202R | 12 | | UB | B | 0-0 | 33-43-11 | D02070 | | 5 | | | | GD01646 | S.. | N | | ALL |
| 203B | 12 | | VG | C | 2-9 | 33-43-11 | D04426J | | 1 | | | | SM00005 | | 9 | | ALL |
| 203R | 12 | | VG | C | 0-0 | 33-43-11 | D04426J | | 2 | | | | SM00004 | | 9 | | ALL |
| 203Z | | | | C | 0-0 | 33-43-11 | GD03722 | | S.. | N | | | GD01644 | S.. | N | *1 | ALL |
| 204B | 12 | | VG | D | 4-1 | 33-43-11 | D04428J | | 1 | | | | SM00008 | | 9 | | ALL |
| 204R | 12 | | VG | D | 0-0 | 33-43-11 | D04428J | | 2 | | | | SM00007 | | 9 | | ALL |
| 204Z | | | | D | 0-0 | 33-43-11 | GD03726 | | S.. | N | | | GD01644 | S.. | N | *2 | ALL |
| 205B | 12 | | VG | E | 67-10 | 33-43-11 | D02070 | | 2 | | | | SM00001 | | 9 | | 050-099, 155-199, 276-299 |
| 205B | 12 | | VG | E | 67-10 | 33-43-11 | SM00003 | | | 9 | | | SM00001 | | 9 | | 150-154, 275 |
| 205R | 12 | | VG | E | 0-0 | 33-43-11 | SM00004 | | | 9 | | | GD01648 | A.. | N | | ALL |
| 205Z | | | | E | 0-0 | 33-43-11 | GD01644 | | S.. | N | *3 | | GD03718 | S.. | N | *1 | ALL |
| 206 | 12 | | UA | | 1-0 | 33-43-11 | D02070 | | 1 | | | | SM00007 | | 9 | | ALL |
| 207 | 12 | | UA | | 1-0 | 33-43-11 | D02070 | | 7 | | | | SM00008 | | 9 | | ALL |
| 208B | 12 | | VG | J | 4-1 | 33-43-11 | D04428J | | 3 | | | | SM00005 | | 9 | | ALL |
| 208R | 12 | | VG | J | 0-0 | 33-43-11 | D04428J | | 4 | | | | SM00007 | | 9 | | ALL |
| 208Z | | | | J | 0-0 | 33-43-11 | GD03726 | | S.. | N | | | GD01644 | S.. | N | *1 | ALL |
| 209B | 12 | | VG | K | 2-9 | 33-43-11 | D04426J | | 3 | | | | SM00008 | | 9 | | ALL |
| 209R | 12 | | VG | K | 0-0 | 33-43-11 | D04426J | | 4 | | | | SM00004 | | 9 | | ALL |
| 209Z | | | | K | 0-0 | 33-43-11 | GD03722 | | S.. | N | | | GD01644 | S.. | N | *2 | ALL |
| 210 | 12 | | VF | L | 67-10 | 33-43-11 | GD01648 | | A.. | N | | | SM00007 | | 9 | | ALL |
| 210Z | | | | L | 0-0 | 33-43-11 | GD01644 | | S.. | N | *3 | | GD03718 | S.. | N | *1 | ALL |
| 211B | 18 | | VG | N | 65-11 | 33-44-21 | D03466 | | 1 | | | | D04380J | | 6 | | ALL |
| 211R | 18 | | VG | N | 0-0 | 33-44-21 | D03466 | | 2 | | | | GD01648 | A.. | N | | ALL |
| 211Z | | | | N | 0-0 | 33-44-21 | GD03714 | | S.. | N | | | GD03718 | S.. | N | | 050-099, 150-154 |
| 211Z | | | | N | 0-0 | 33-44-21 | GD03714 | | S.. | N | | | GD03718 | S.. | N | *2 | 155-199, 275-299 |
| 213B | 18 | | VG | S | 5-1 | SPARE | D02382 | | CAP | Y | | | D04380J | | 2 | | 155-199 |

WIRE LIST

D280T132

91-21-11

Section W0470

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|---------|-------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0470 | 286T0470 | | | R WING OUTBD FS-R2-LIGHTING (continued) | | | | | | | | | | | |
| 213B | 18 | VG | S | | 5-1 | 30-11-11 | D02382 | | 1 | DK | D04380J | | 2 | | 275-299 |
| 213R | 18 | VG | S | | 0-0 | SPARE | D02382 | | | CAP Y | D04380J | | 3 | | 155-199 |
| 213R | 18 | VG | S | | 0-0 | 30-11-11 | D02382 | | | 2 | DK | D04380J | | 3 | 275-299 |
| 213Z | | | S | | 0-0 | SPARE | GD03732 | | S.. | N | GD03718 | S.. | N | *2 | 155-199, 275-299 |
| W0471 | 286T0471 | | | MISC ELEC EQUIPMENT L, P36 TO P33 & SHELVES | | | | | | | | | | | |
| 001 | 22 | PA | | | 16-0 | 22-14-31 | D04457J | | | 1 | D05433P | | 1 | | ALL |
| 002 | 22 | PA | | | 16-0 | 22-14-31 | D04457J | | | 2 | D05433P | | 2 | | ALL |
| 003 | 22 | PA | | | 16-0 | 34-46-12 | D04457J | | | 3 | D05433P | | 3 | | ALL |
| 006 | 24 | PK | | | 24-0 | 34-12-12 | D04457J | | | 23 | D04801P | | 3 | | ALL |
| 007 | 24 | PK | | | 16-0 | 22-32-15 | D04457J | | | 7 | D05433P | | 7 | | ALL |
| 008 | 24 | PK | | | 16-0 | 22-32-15 | D04457J | | | 8 | D05433P | | 8 | | ALL |
| 012 | 24 | PK | | | 16-0 | 34-12-12 | D04457J | | | 16 | D05433P | | 16 | | ALL |
| 013 | 24 | PK | | | 16-0 | 34-12-12 | D04457J | | | 17 | D05433P | | 17 | | ALL |
| 014 | 24 | PK | | | 24-0 | 34-12-12 | D04457J | | | 18 | D04801P | | 8 | | ALL |
| 015 | 24 | PK | | | 24-0 | 34-12-12 | D04457J | | | 19 | D04801P | | 9 | | ALL |
| 016 | 24 | PK | | | 24-0 | 34-12-12 | D04457J | | | 20 | D04801P | | 10 | | ALL |
| 017 | 24 | PK | | | 24-0 | SPARE | D04457J | | | | CAP Y | D04801P | CAP Y | | ALL |
| 018 | 22 | PA | | | 20-0 | 31-31-11 | D04711J | | | 8 | D05433P | | 18 | | ALL |
| 022 | 24 | PK | | | 19-0 | 34-61-14 | D04791J | | | 2 | D05433P | | 21 | | ALL |
| 023 | 24 | PK | | | 19-0 | 34-53-11 | D04791J | | | 3 | D05433P | | 22 | | ALL |
| 024 | 24 | PK | | | 28-0 | SPARE | D04791J | | | 1 | D04801P | | 1 | | 050-099, 150-154, 275-299 |
| 025 | 24 | PK | | | 28-0 | 31-31-13 | D04711J | | | 18 | D04801P | | 18 | | ALL |
| 026 | 22 | PA | | | 20-0 | 31-31-11 | D04711J | | | 23 | D05433P | | 43 | | ALL |
| 027 | 22 | PA | | | 20-0 | 31-31-11 | D04711J | | | 24 | D05433P | | 44 | | ALL |
| 031 | 22 | PA | | | 25-6 | SPARE | D05817J | | | 2 | D04801P | | 2 | | ALL |
| 033 | 20 | PA | | | 20-0 | SPARE | D04791J | | | 6 | D05431P | | 6 | | ALL |
| 035 | 24 | PK | | | 24-0 | 22-41-11 | D04801P | | | 22 | D04457J | | 52 | | ALL |
| 036 | 22 | PA | | | 17-6 | SPARE | D05817J | | | 5 | D05431P | | 5 | | ALL |
| 040 | 24 | PK | | | 17-5 | 27-32-11 | D05817J | | | 15 | D05433P | | 35 | | ALL |
| 041 | 24 | PK | | | 16-0 | 34-55-11 | D04457J | | | 26 | D05433P | | 36 | | ALL |
| 043 | 20 | PA | | | 19-0 | SPARE | D05433P | | | 53 | D04791J | | 5 | | 050-099 |
| 043 | 20 | PA | | | 20-0 | SPARE | D05433P | | | 53 | D04791J | | 5 | | 150-199, 275-299 |
| 045 | 20 | PA | | | 17-5 | 38-32-11 | D05433P | | | 39 | D05817J | | 10 | | 050-099, 150-199, 277-299 |
| 045 | 22 | PA | | | 17-5 | SPARE | D05433P | | | 39 | D05817J | | 10 | | 275 |
| 045 | 20 | PA | | | 17-5 | SPARE | D05433P | | | 39 | D05817J | | 10 | | 276 |
| 047 | 22 | PA | | | 12-0 | SPARE | D05431P | | | | CAP Y | D04801P | CAP Y | | 150-152 |

WIRE LIST

D280T132

91-21-11

Section W0470

Page 2

Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0471 | 286T0471 | | | MISC ELEC EQUIPMENT L, P36 TO P33 & SHELVES (continued) | | | | | | | | | | | | | |
| 047 | 22 | | PA | 12-0 | SPARE | D05431P | | 13 | | | | | D04801P | CAP | Y | | 275-276 |
| 049 | 24 | | PK | 24-0 | SPARE | D04457J | | 35 | | | | | D04801P | 23 | | | 050-099 |
| 049 | 24 | | PK | 24-0 | 30-34-31 | D04457J | | 35 | | | | | D04801P | 23 | | | 150-199 |
| 050 | 24 | | PK | 16-0 | 32-42-11 | D04457J | | 30 | | | | | D05433P | 10 | | | ALL |
| 051 | 24 | | PK | 24-0 | 22-32-13 | D04801P | | 7 | | | | | D04457J | 22 | | | ALL |
| 052 | 24 | | PK | 28-0 | SPARE | D04801P | | CAP | Y | | | | D04791J | 21 | | | ALL |
| 062 | 24 | | PK | 20-0 | 31-31-21 | D05431P | | 22 | | | | | D04711J | 32 | | | ALL |
| 064 | 24 | | PK | 20-0 | 31-31-21 | D05431P | | 24 | | | | | D04711J | 34 | | | ALL |
| 066 | 24 | | PK | 16-0 | SPARE | D04457J | | CAP | Y | | | | D05431P | 19 | | | ALL |
| 067 | 24 | | PK | 16-0 | SPARE | D04457J | | 38 | | | | | D05433P | 38 | | | 050-099, 150-199 |
| 068 | 22 | | PA | 11-4 | 27-09-13 | D05433P | | 41 | | | | | D04801P | 14 | | | ALL |
| 069 | 22 | | PA | 11-4 | 27-09-13 | D05433P | | 42 | | | | | D04801P | 15 | | | ALL |
| 070 | 16 | | PA | 16-0 | 27-32-31 | D04457J | | 51 | FM | | | | D05433P | 51 | FM | | ALL |
| 071 | 16 | | PA | 16-0 | 27-32-31 | D04457J | | 55 | FM | | | | D05433P | 55 | FM | | ALL |
| 072 | 20 | | PA | 16-0 | 27-32-31 | D04457J | | 34 | | | | | D05433P | 34 | | | ALL |
| 074 | 24 | | PK | 21-0 | 34-61-15 | D05497P | | 1 | | | | | D04791J | 22 | | | ALL |
| 077 | 24 | | PK | 21-0 | 34-61-16 | D05497P | | 13 | | | | | D04791J | 23 | | | 050-099 |
| 077 | 24 | | PK | 20-0 | 34-61-15 | D05497P | | 13 | | | | | D04791J | 23 | | | 150-199 |
| 077 | 24 | | PK | 21-0 | 34-61-15 | D05497P | | 13 | | | | | D04791J | 23 | | | 275-299 |
| 078 | 24 | | PK | 20-0 | 31-31-13 | D04711J | | 12 | | | | | D05433P | 32 | | | ALL |
| 079 | 24 | | PK | 20-0 | 31-31-13 | D04711J | | 13 | | | | | D05433P | 33 | | | ALL |
| 085 | 22 | | PA | 16-0 | 34-22-16 | D04457J | | 29 | | | | | D05433P | 19 | | | ALL |
| 086 | 22 | | PA | 17-6 | 34-22-36 | D05817J | | 4 | | | | | D05431P | 18 | | | ALL |
| 089 | 24 | | PK | 22-0 | 31-31-26 | D05497P | | 14 | | | | | D04711J | 36 | | | ALL |
| 090 | 24 | | PK | 22-0 | 31-31-26 | D05497P | | 15 | | | | | D04711J | 37 | | | ALL |
| 091 | 24 | | PK | 18-8 | 21-61-61 | D05817J | | 3 | | | | | D05497P | 22 | | | ALL |
| 092 | 24 | | PK | 18-8 | 21-61-61 | D05817J | | 6 | | | | | D05497P | 20 | | | ALL |
| 093 | 24 | | PK | 18-8 | 21-61-61 | D05817J | | 16 | | | | | D05497P | 21 | | | ALL |
| 094 | 24 | | PK | 17-5 | 21-61-71 | D05817J | | 17 | | | | | D05433P | 40 | | | 150-199, 275-299 |
| 095 | 24 | | PK | 17-5 | 21-61-71 | D05817J | | 18 | | | | | D05433P | 45 | | | ALL |
| 096 | 24 | | PK | 17-5 | 21-61-71 | D05817J | | 19 | | | | | D05433P | 54 | | | ALL |
| 097 | 24 | | PK | 18-8 | 21-61-71 | D05817J | | 22 | | | | | D05497P | 23 | | | ALL |
| 098 | 24 | | PK | 18-8 | 21-61-71 | D05817J | | 23 | | | | | D05497P | 24 | | | ALL |
| 109 | 24 | | PK | 18-0 | 21-61-71 | D05433P | | 40 | | | | | D05817J | 17 | | | 050-099 |
| 110 | 22 | | PA | 16-0 | 34-45-13 | D05431P | | 17 | | | | | D04457J | 13 | | | 050-099, 150-152, 155-199, 277-299 |
| 110 | 22 | | PA | 16-0 | 34-45-13 | D05431P | | 23 | | | | | D04457J | 13 | | | 153-154 |
| 117 | 22 | | PA | 20-0 | 78-36-11 | D05433P | | 20 | | | | | D07160J | 1 | | | ALL |
| 118 | 22 | | PA | 20-0 | 78-36-11 | D05433P | | 37 | | | | | D07160J | 2 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0470

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|----|-----|---|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0471 | 286T0471 | | | MISC ELEC EQUIPMENT L, P36 TO P33 & SHELVES (continued) | | | | | | | | | | | | | | | |
| 119 | 22 | | PA | | 20-0 | 78-36-11 | D05433P | | | | 48 | | | | D07160J | 7 | | | ALL |
| 120 | 22 | | PA | | 20-0 | 78-36-11 | D05433P | | | | 49 | | | | D07160J | 4 | | | ALL |
| 121 | 22 | | PA | | 20-0 | 78-36-11 | D05433P | | | | 50 | | | | D07160J | 3 | | | ALL |
| 122 | 22 | | PA | | 25-0 | 78-36-11 | D04801P | | | | 4 | | | | D07160J | 8 | | | ALL |
| 123 | 22 | | PA | | 25-0 | 78-36-11 | D04801P | | | | 12 | | | | D07160J | 6 | | | ALL |
| 124 | 22 | | PA | | 25-0 | 78-36-11 | D04801P | | | | 13 | | | | D07160J | 5 | | | ALL |
| 125 | 22 | | PA | | 25-0 | 78-36-11 | D04801P | | | | 17 | | | | D07160J | 9 | | | ALL |
| 201B | 22 | | PB | IA | 16-0 | | SPARE | | | | 10 | | | | D05431P | 10 | | | 275-299 |
| 201R | 22 | | PB | IA | 0-0 | | SPARE | | | | 9 | | | | D05431P | 9 | | | 275-299 |
| 202B | 24 | | PL | IB | 16-0 | | SPARE | | | | 12 | | | | D05431P | 12 | | | 275-299 |
| 202R | 24 | | PL | IB | 0-0 | | SPARE | | | | 11 | | | | D05431P | 11 | | | 275-299 |
| 209B | 24 | | PL | II | 28-0 | 31-31-13 | D04711J | | | | 16 | | | | D04801P | 6 | | | ALL |
| 209R | 24 | | PL | II | 0-0 | 31-31-13 | D04711J | | | | 15 | | | | D04801P | 5 | | | ALL |
| 210B | 24 | | PL | IJ | 28-0 | 31-31-13 | D04711J | | | | 20 | | | | D04801P | 20 | | | ALL |
| 210R | 24 | | PL | IJ | 0-0 | 31-31-13 | D04711J | | | | 19 | | | | D04801P | 19 | | | ALL |
| 214B | 24 | | PW | IN | 16-0 | 73-21-14 | D05433P | | | | 28 | | | | D04457J | 46 | | | ALL |
| 214R | 24 | | PW | IN | 0-0 | 73-21-14 | D05433P | | | | 27 | | | | D04457J | 45 | | | ALL |
| 214Z | | | | IN | 0-0 | 73-21-14 | D05433P | | | | 29 | | | | D04457J | 47 | | | ALL |
| 215B | 24 | | PW | IO | 16-0 | 73-21-14 | D05431P | | | | 2 | | | | D04457J | 32 | | | ALL |
| 215R | 24 | | PW | IO | 0-0 | 73-21-14 | D05431P | | | | 1 | | | | D04457J | 31 | | | ALL |
| 215Z | | | | IO | 0-0 | 73-21-14 | D05431P | | | | 3 | | | | D04457J | 33 | | | ALL |
| 216B | 22 | | PB | IP | 16-0 | | SPARE | | | | | CAP | Y | | D04457J | | CAP | Y | 150-152 |
| 216B | 22 | | PB | IP | 16-0 | | SPARE | | | | 15 | | | | D04457J | | CAP | Y | 275-276 |
| 216R | 22 | | PB | IP | 0-0 | | SPARE | | | | | CAP | Y | | D04457J | | CAP | Y | 150-152 |
| 216R | 22 | | PB | IP | 0-0 | | SPARE | | | | 14 | | | | D04457J | | CAP | Y | 275-276 |
| 217B | 24 | | PL | IQ | 20-0 | | SPARE | | | | 27 | | | | D05431P | | CAP | Y | 150-152 |
| 217B | 24 | | PL | IQ | 20-0 | | SPARE | | | | 27 | | | | D05431P | 17 | | | 153-154, 275-276 |
| 217R | 24 | | PL | IQ | 0-0 | | SPARE | | | | 26 | | | | D05431P | 16 | | | 150-154, 275-276 |
| 218B | 24 | | PW | IR | 16-0 | 32-42-11 | D04457J | | | | 43 | | | | D05433P | 24 | | | ALL |
| 218R | 24 | | PW | IR | 0-0 | 32-42-11 | D04457J | | | | 42 | | | | D05433P | 23 | | | ALL |
| 218Z | | | | IR | 0-0 | 32-42-11 | D04457J | | | | 44 | | | | D05433P | 25 | | | ALL |
| 219B | 24 | | PW | IS | 21-0 | 34-61-15 | D05497P | | | | 8 | | | | D04791J | 7 | | | ALL |
| 219R | 24 | | PW | IS | 0-0 | 34-61-15 | D05497P | | | | 9 | | | | D04791J | 8 | | | ALL |
| 219Z | | | | IS | 0-0 | 34-61-15 | D05497P | | | | 10 | | | | D04791J | 9 | | | ALL |
| 220B | 24 | | PW | IT | 21-0 | 34-61-15 | D05497P | | | | 2 | | | | D04791J | 10 | | | ALL |
| 220R | 24 | | PW | IT | 0-0 | 34-61-15 | D05497P | | | | 3 | | | | D04791J | 11 | | | ALL |
| 220Z | | | | IT | 0-0 | 34-61-15 | D05497P | | | | 4 | | | | D04791J | 17 | | | ALL |
| 221B | 24 | | PW | IU | 21-0 | 34-61-15 | D05497P | | | | 5 | | | | D04791J | 18 | | | ALL |
| 221R | 24 | | PW | IU | 0-0 | 34-61-15 | D05497P | | | | 6 | | | | D04791J | 19 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0470
 Page 4
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0471 | 286T0471 | | | MISC ELEC EQUIPMENT L, P36 TO P33 & SHELVES (continued) | | | | | | | | | | | | |
| 221Z | | | IU | 0-0 | 34-61-15 | D05497P | | 7 | | | D04791J | | 20 | | ALL | |
| 223B | 24 | PW | IW | 17-5 | 27-32-11 | D05433P | | 47 | | | D05817J | | 13 | | ALL | |
| 223R | 24 | PW | IW | 0-0 | 27-32-11 | D05433P | | 46 | | | D05817J | | 12 | | ALL | |
| 223Z | | | IW | 0-0 | 27-32-11 | D05433P | | 52 | | | D05817J | | 14 | | ALL | |
| 224B | 24 | PW | IX | 16-0 | 73-21-14 | D04457J | | 54 | | | D05433P | | 14 | | 050-099 | |
| 224B | 24 | PW | IX | 16-0 | 73-21-14 | D05433P | | 14 | | | D04457J | | 54 | | 150-199, 275-299 | |
| 224R | 24 | PW | IX | 0-0 | 73-21-14 | D04457J | | 53 | | | D05433P | | 13 | | 050-099 | |
| 224R | 24 | PW | IX | 0-0 | 73-21-14 | D05433P | | 13 | | | D04457J | | 53 | | 150-199, 275-299 | |
| 224Z | | | IX | 0-0 | 73-21-14 | D04457J | | 36 | | | D05433P | | 15 | | 050-099 | |
| 224Z | | | IX | 0-0 | 73-21-14 | D05433P | | 15 | | | D04457J | | 36 | | 150-199, 275-299 | |
| 228B | 24 | PW | JC | 16-0 | SPARE | D04457J | | 5 | | | D05433P | | 12 | | 050-099, 162-199, 280-299 | |
| 228B | 24 | PW | JC | 16-0 | 77-12-11 | D04457J | | 5 | | | D05433P | | 12 | | 150-157, 275-276 | |
| 228R | 24 | PW | JC | 0-0 | SPARE | D04457J | | 4 | | | D05433P | | 11 | | 050-099, 162-199, 280-299 | |
| 228R | 24 | PW | JC | 0-0 | 77-12-11 | D04457J | | 4 | | | D05433P | | 11 | | 150-157, 275-276 | |
| 228Z | | | JC | 0-0 | SPARE | D04457J | | 6 | | | D05433P | | 9 | | 050-099, 162-199, 280-299 | |
| 228Z | | | JC | 0-0 | 77-12-11 | D04457J | | 6 | | | D05433P | | 9 | | 150-157, 275-276 | |
| 238B | 24 | PL | JM | 18-8 | 21-61-61 | D05817J | | 8 | | | D05497P | | 11 | | ALL | |
| 238R | 24 | PL | JM | 0-0 | 21-61-61 | D05817J | | 7 | | | D05497P | | 12 | | ALL | |
| 239B | 24 | PL | JN | 17-6 | 21-61-71 | D05817J | | 21 | | | D05431P | | 21 | | ALL | |
| 239R | 24 | PL | JN | 0-0 | 21-61-71 | D05817J | | 20 | | | D05431P | | 20 | | ALL | |
| 244B | 24 | PW | JS | 19-0 | 31-35-14 | D04791J | | 14 | | | D05433P | | 5 | | 050-099, 150-199, 275-276, 278-299 | |
| 244R | 24 | PW | JS | 0-0 | 31-35-14 | D04791J | | 13 | | | D05433P | | 4 | | 050-099, 150-199, 275-276, 278-299 | |
| 244Z | | | JS | 0-0 | 31-35-14 | D04791J | | 15 | | | D05433P | | 6 | | 050-099, 150-199, 275-276, 278-299 | |
| 245B | 24 | PW | JT | 17-0 | 34-45-14 | D06141J | | 2 | | | D05431P | | 13 | | 050-099, 155-199, 277-299 | |
| 245B | 24 | PW | JT | 16-0 | 34-45-14 | D06141J | | 2 | | | D05431P | | 13 | | 150-154 | |
| 245R | 24 | PW | JT | 0-0 | 34-45-14 | D06141J | | 1 | | | D05431P | | 14 | | 050-099, 150-199, 277-299 | |
| 245Z | | | JT | 0-0 | 34-45-14 | D06141J | | 3 | | | D05431P | | 15 | | 050-099, 150-199, 277-299 | |
| 70L | 20 | PA | | 24-0 | 29-11-14 | D04801P | | 21 | | | D04457J | | 28 | | ALL | |
| 70M | 20 | PQ | CT | 24-0 | 29-11-14 | D04801P | | 24 | | | D04457J | | 24 | | ALL | |
| 70MZ | | | CT | 0-0 | 29-11-14 | D04801P | | DED | | | D04457J | | DED | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0470

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0471 | 286T0471 | | | MISC ELEC EQUIPMENT L, P36 TO P33 & SHELVES (continued) | | | | | | | | | | | |
| 70N | 20 | | PA | | 24-0 | 29-11-14 | D04801P | | 11 | | D04457J | | 15 | | ALL |
| 70P | 20 | | PA | | 24-0 | 29-11-14 | D04801P | | 16 | | D04457J | | 21 | | ALL |
| 904B | 24 | | PW | AB | 0-0 | 34-53-11 | D04791J | | 16 | | D05431P | | 8 | | 275-299 |
| 904R | 24 | | PW | AB | 10-0 | 34-53-11 | D04791J | | 12 | | D05431P | | 7 | | 275-299 |
| 904Z | | | | AB | 0-0 | 34-53-11 | D04791J | | 24 | | D05431P | | 4 | | 275-299 |
| W0472 | 286T0472 | | | L WING OUTBD FS-S2-FUELING PNL | | | | | | | | | | | |
| 001 | 20 | | VF | A | 25-10 | 28-21-11 | D04744P | | 5 | | D04442J | | 1 | | ALL |
| 001Z | | | | A | 0-0 | 28-21-11 | GD04362 | S.. | N | *2 | GD04354 | S.. | N | *1 | ALL |
| 002 | 20 | | VF | C | 25-10 | 28-21-12 | D04744P | | 8 | | D04442J | | 4 | | ALL |
| 002Z | | | | C | 0-0 | 28-21-12 | GD04364 | S.. | N | *1 | GD04354 | S.. | N | *1 | ALL |
| 003 | 20 | | VF | D | 25-10 | 28-21-12 | D04744P | | 9 | | D04442J | | 5 | | ALL |
| 003Z | | | | D | 0-0 | 28-21-12 | GD04364 | S.. | N | *2 | GD04354 | S.. | N | *1 | ALL |
| 004 | 18 | | VF | BG | 27-2 | 28-21-12 | D04744P | | 16 | | GD04276 | D.. | N | | ALL |
| 004Z | | | | BG | 0-0 | 28-21-12 | GD04362 | S.. | N | *2 | GD04354 | S.. | N | *4 | ALL |
| 007 | 18 | | VF | H | 30-0 | 28-21-11 | D04744P | | 19 | | D04444J | | 30 | | 050-099, 150-156, 162-166, 275-276 |
| 007 | 18 | | VF | H | 25-7 | 28-21-11 | D04744P | | 19 | | D04444J | | 30 | | 157, 167-199, 277-299 |
| 007Z | | | | H | 0-0 | 28-21-11 | GD04364 | S.. | N | *1 | GD04356 | S.. | N | *1 | 050-099, 150-156, 162-166, 275-276 |
| 007Z | | | | H | 0-0 | 28-21-11 | GD04364 | S.. | N | *1 | GD04356 | S.. | N | *4 | 157, 167-199, 277-299 |
| 008 | 18 | | VF | I | 25-10 | 28-41-12 | D04744P | | 17 | | D04442J | | 10 | | ALL |
| 008Z | | | | I | 0-0 | 28-41-12 | GD04362 | S.. | N | *2 | GD04354 | S.. | N | *3 | ALL |
| 009 | 18 | | UA | | 2-0 | 28-21-11 | D04744P | | 29 | | GD03530 | S.. | N | | ALL |
| 010 | 20 | | VF | P | 25-7 | 28-26-11 | D04746P | | 7 | | D04444J | | 7 | | ALL |
| 010Z | | | | P | 0-0 | 28-26-11 | GD04360 | S.. | N | *4 | GD04356 | S.. | N | *1 | ALL |
| 011 | 20 | | VF | Q | 25-7 | 28-26-11 | D04746P | | 8 | | D04444J | | 8 | | ALL |
| 011Z | | | | Q | 0-0 | 28-26-11 | GD04360 | S.. | N | *4 | GD04356 | S.. | N | *1 | ALL |
| 012 | 20 | | VF | R | 25-7 | 28-21-11 | D04744P | | 1 | | D04444J | | 9 | | ALL |
| 012Z | | | | R | 0-0 | 28-21-11 | GD04362 | S.. | N | *1 | GD04356 | S.. | N | *3 | ALL |
| 013 | 20 | | VF | S | 25-7 | 28-21-13 | D04744P | | 22 | | D04444J | | 10 | | ALL |
| 013Z | | | | S | 0-0 | 28-21-13 | GD04364 | S.. | N | *2 | GD04356 | S.. | N | *3 | ALL |
| 014 | 20 | | VF | T | 25-7 | 28-21-13 | D04744P | | 3 | | D04444J | | 11 | | ALL |
| 014Z | | | | T | 0-0 | 28-21-13 | GD04362 | S.. | N | *1 | GD04356 | S.. | N | *3 | ALL |
| 015 | 20 | | VF | V | 25-7 | 28-21-11 | D04744P | | 4 | | D04444J | | 12 | | ALL |
| 015Z | | | | V | 0-0 | 28-21-11 | GD04362 | S.. | N | *1 | GD04356 | S.. | N | *2 | ALL |
| 016 | 20 | | VF | Z | 25-7 | 28-26-11 | D04746P | | 17 | | D04444J | | 17 | | ALL |
| 016Z | | | | Z | 0-0 | 28-26-11 | GD04360 | S.. | N | *4 | GD04358 | S.. | N | *1 | ALL |
| 017 | 20 | | VF | AA | 25-7 | 28-26-11 | D04746P | | 18 | | D04444J | | 18 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0470

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|---------|-------|------|------|--|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0472 | 286T0472 | | | L WING OUTBD FS-S2-FUELING PNL (continued) | | | | | | | | | | | |
| 017Z | | | | AA | 0-0 | 28-26-11 | GD04360 | S.. | N | *4 | GD04358 | S.. | N | *1 | ALL |
| 018 | 20 | VF | | AB | 25-7 | 28-21-11 | D04744P | 11 | | | D04444J | 13 | | | ALL |
| 018Z | | | | AB | 0-0 | 28-21-11 | GD04364 | S.. | N | *3 | GD04356 | S.. | N | *2 | ALL |
| 019 | 20 | VF | | AC | 25-7 | 28-21-13 | D04744P | 12 | | | D04444J | 15 | | | ALL |
| 019Z | | | | AC | 0-0 | 28-21-13 | GD04362 | S.. | N | *3 | GD04358 | S.. | N | *2 | ALL |
| 01TB | 20 | 2Z | | BD | 27-6 | 23-41-11 | SP00854 | 9 | | | D04444J | 25 | | | ALL |
| 01TI | | | | BD | 0-0 | 23-41-11 | SP00856 | 9 | | | D04444J | 27 | | | ALL |
| 01TO | | | | BD | 0-0 | 23-41-11 | GD04366 | S.. | N | | GD04356 | S.. | N | *1 | 050-099, 150-156, 162-166, 275-276 157, 167-199, 277-299 |
| 01TO | | | | BD | 0-0 | 23-41-11 | GD04366 | S.. | N | | GD04356 | S.. | N | *4 | ALL |
| 01TR | 20 | 2Z | | BD | 0-0 | 23-41-11 | SP00852 | 9 | | | D04444J | 26 | | | ALL |
| 020 | 20 | VF | | AD | 25-7 | 28-21-13 | D04744P | 13 | | | D04444J | 16 | | | ALL |
| 020Z | | | | AD | 0-0 | 28-21-13 | GD04362 | S.. | N | *3 | GD04358 | S.. | N | *2 | ALL |
| 021 | 20 | VF | | AE | 25-7 | 28-21-11 | D04744P | 14 | | | D04444J | 14 | | | ALL |
| 021Z | | | | AE | 0-0 | 28-21-11 | GD04362 | S.. | N | *3 | GD04356 | S.. | N | *2 | ALL |
| 024 | 20 | VF | | AK | 25-10 | 28-21-11 | D04744P | 21 | | | D04442J | 13 | | | ALL |
| 024Z | | | | AK | 0-0 | 28-21-11 | GD04364 | S.. | N | *1 | GD04354 | S.. | N | *4 | ALL |
| 025 | 20 | VF | | AL | 25-10 | 28-21-13 | D04744P | 2 | | | D04442J | 15 | | | ALL |
| 025Z | | | | AL | 0-0 | 28-21-13 | GD04362 | S.. | N | *1 | GD04354 | S.. | N | *4 | ALL |
| 026 | 20 | VF | | AM | 25-10 | 28-21-13 | D04744P | 23 | | | D04442J | 16 | | | ALL |
| 026Z | | | | AM | 0-0 | 28-21-13 | GD04364 | S.. | N | *2 | GD04354 | S.. | N | *3 | ALL |
| 027 | 20 | VF | | AN | 25-10 | 28-21-11 | D04744P | 24 | | | D04442J | 14 | | | ALL |
| 027Z | | | | AN | 0-0 | 28-21-11 | GD04364 | S.. | N | *3 | GD04354 | S.. | N | *1 | ALL |
| 034 | 20 | VF | | AU | 25-10 | 28-26-11 | D04744P | 10 | | | D04442J | 30 | | | ALL |
| 034Z | | | | AU | 0-0 | 28-26-11 | GD04364 | S.. | N | *2 | GD04354 | S.. | N | *3 | ALL |
| 037 | 20 | VF | | BE | 25-7 | 28-41-11 | D04744P | 6 | | | D04444J | 28 | | | ALL |
| 037Z | | | | BE | 0-0 | 28-41-11 | GD04362 | S.. | N | *2 | GD04358 | S.. | N | *2 | ALL |
| 038 | 20 | VF | | BF | 25-7 | 28-41-11 | D04744P | 7 | | | D04444J | 29 | | | ALL |
| 038Z | | | | BF | 0-0 | 28-41-11 | GD04364 | S.. | N | *1 | GD04358 | S.. | N | *2 | ALL |
| 039 | 20 | VF | | CA | 25-7 | 28-41-11 | D04444J | 19 | | | D04746P | 11 | | | ALL |
| 039Z | | | | CA | 0-0 | 28-41-11 | GD04358 | S.. | N | *1 | GD04360 | S.. | N | *2 | ALL |
| 040 | 20 | VF | | CB | 25-7 | 28-41-11 | D04444J | 1 | | | D04746P | 1 | | | ALL |
| 040Z | | | | CB | 0-0 | 28-41-11 | GD04356 | S.. | N | *1 | GD04360 | S.. | N | *1 | ALL |
| 203B | 20 | VG | | M | 25-7 | 28-41-11 | D04746P | 3 | | | D04444J | 3 | | | ALL |
| 203R | 20 | VG | | M | 0-0 | 28-41-11 | D04746P | 4 | | | D04444J | 4 | | | ALL |
| 203Z | | | | M | 0-0 | 28-41-11 | GD04360 | S.. | N | *1 | GD04356 | S.. | N | *2 | ALL |
| 206B | 20 | VG | | X | 25-7 | 28-41-11 | D04746P | 13 | | | D04444J | 21 | | | ALL |
| 206R | 20 | VG | | X | 0-0 | 28-41-11 | D04746P | 14 | | | D04444J | 22 | | | ALL |
| 206Z | | | | X | 0-0 | 28-41-11 | GD04360 | S.. | N | *1 | GD04358 | S.. | N | *1 | ALL |

WIRE LIST

D280T132

91-21-11

Section W0470

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|--------------|-----------------|---|-------|-------------|----------|---------|---------|-------|------|------|---------|-------|------|------|--------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0472 | 286T0472 | L WING OUTBD FS-S2-FUELING PNL (continued) | | | | | | | | | | | | | |
| 209B | 20 | VG | AG | 25-10 | 28-41-11 | D04746P | | 23 | | | D04442J | 21 | | | ALL |
| 209R | 20 | VG | AG | 0-0 | 28-41-11 | D04746P | | 24 | | | D04442J | 22 | | | ALL |
| 209Z | | | AG | 0-0 | 28-41-11 | GD04360 | | S.. | N | *2 | GD04354 | S.. | N | *2 | ALL |
| 214B | 20 | VG | G | 30-0 | 28-21-11 | SP01982 | | | | | GD04276 | D.. | N | | ALL |
| 214R | 20 | VG | G | 0-0 | 28-21-11 | SP00516 | | | | | D04442J | 25 | | | ALL |
| 214Z | | | G | 0-0 | 28-21-11 | GD03688 | | S.. | N | | GD04354 | S.. | N | *3 | ALL |
| 215B | 20 | VG | AP | 30-9 | 28-21-11 | SP01984 | | | | | GD04276 | D.. | N | | ALL |
| 215R | 20 | VG | AP | 0-0 | 28-21-11 | SP00616 | | | | | D04442J | 9 | | | ALL |
| 215Z | | | AP | 0-0 | 28-21-11 | GD04366 | | S.. | N | | GD04354 | S.. | N | *2 | ALL |
| 216B | 20 | VG | AR | 28-10 | 28-21-11 | D04746P | | | | | GD04276 | D.. | N | | ALL |
| 216R | 20 | VG | AR | 0-0 | 28-21-11 | D04746P | | | | | D04442J | 8 | | | ALL |
| 216Z | | | AR | 0-0 | 28-21-11 | GD04360 | | S.. | N | *2 | GD04354 | S.. | N | *2 | ALL |
| 301B | 20 | VH | L | 25-10 | 28-41-11 | D04442J | | | | | D04746P | 25 | | | ALL |
| 301R | 20 | VH | L | 0-0 | 28-41-11 | D04442J | | | | | D04746P | 26 | | | ALL |
| 301Y | 20 | VH | L | 0-0 | 28-41-11 | D04442J | | | | | D04746P | 22 | | | ALL |
| 301Z | | | L | 0-0 | 28-41-11 | GD04354 | | S.. | N | *2 | GD04360 | S.. | N | *2 | ALL |
| 302B | 20 | VH | N | 25-7 | 28-41-11 | D04444J | | | | | D04746P | 15 | | | ALL |
| 302R | 20 | VH | N | 0-0 | 28-41-11 | D04444J | | | | | D04746P | 16 | | | ALL |
| 302Y | 20 | VH | N | 0-0 | 28-41-11 | D04444J | | | | | D04746P | 12 | | | ALL |
| 302Z | | | N | 0-0 | 28-41-11 | GD04356 | | S.. | N | *3 | GD04360 | S.. | N | | ALL |
| 303B | 20 | VH | W | 25-7 | 28-41-11 | D04444J | | | | | D04746P | 5 | | | ALL |
| 303R | 20 | VH | W | 0-0 | 28-41-11 | D04444J | | | | | D04746P | 6 | | | ALL |
| 303Y | 20 | VH | W | 0-0 | 28-41-11 | D04444J | | | | | D04746P | 2 | | | ALL |
| 303Z | | | W | 0-0 | 28-41-11 | GD04356 | | S.. | N | *1 | GD04360 | S.. | N | *1 | ALL |
| 401B | 20 | U4 | J | 25-10 | 28-21-11 | D04744P | | | | | D04442J | 26 | | | ALL |
| 401G | 20 | U4 | J | 0-0 | 28-21-11 | D04744P | | | | | D04442J | 27 | | | ALL |
| 401R | 20 | U4 | J | 0-0 | 28-21-11 | D04744P | | | | | D04442J | 28 | | | ALL |
| 401Y | 20 | U4 | J | 0-0 | 28-21-11 | D04744P | | | | | D04442J | 29 | | | ALL |
| 401Z | | | J | 0-0 | 28-21-11 | GD04362 | | S.. | N | *3 | GD04354 | S.. | N | *3 | ALL |
| A-A | | | AS | 0-0 | 28-21-11 | L00062 | | | BLK | | SP00616 | | 9 | | ALL |
| A-B | | | AS | 0-0 | 28-21-11 | L00062 | | | WHT | | SP01984 | | 9 | | ALL |
| A-C | | | AT | 0-0 | 28-21-11 | S00346 | | | RED | | SP00516 | | 9 | | ALL |
| A-D | | | AT | 0-0 | 28-21-11 | S00346 | | | BLU | | SP01982 | | 9 | | ALL |
| A-E | | | BC | 0-0 | 23-41-11 | SP00852 | | | | 9 | D08549 | | RED | | ALL |
| A-F | | | BC | 0-0 | 23-41-11 | SP00854 | | | | 9 | D08549 | | BLU | | ALL |
| A-G | | | BC | 0-0 | 23-41-11 | SP00856 | | | | 9 | D08549 | | BLK | | ALL |
| W0473 | 286T0473 | P37 TO E2-3 SHELF | | | | | | | | | | | | | |
| 003 | 22 | PA | | 15-0 | SPARE | D04667J | | | | 32 | D05435P | 3 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0470
Page 8
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|--------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0473 | 286T0473 | | | P37 TO E2-3 SHELF (continued) | | | | | | | | | | | | |
| 006 | 24 | | PK | 3-0 | SPARE | D05439J | | 6 | | | | | D04667J | 6 | | ALL |
| 007 | 24 | | PK | 3-0 | SPARE | D05439J | | 7 | | | | | D04667J | 7 | | ALL |
| 008 | 24 | | PK | 15-0 | 32-42-11 | D04667J | | 29 | | | | | D05435P | 43 | | ALL |
| 009 | 22 | | PA | 15-0 | 34-12-21 | D04667J | | 13 | | | | | D05435P | 13 | | ALL |
| 010 | 22 | | PA | 15-0 | 34-12-21 | D04667J | | 14 | | | | | D05435P | 14 | | ALL |
| 011 | 22 | | PA | 15-0 | 34-12-21 | D04667J | | 15 | | | | | D05435P | 15 | | ALL |
| 012 | 24 | | PK | 15-0 | 34-12-22 | D04667J | | 16 | | | | | D05435P | 16 | | ALL |
| 013 | 24 | | PK | 15-0 | 34-12-22 | D04667J | | 17 | | | | | D05435P | 17 | | ALL |
| 014 | 24 | | PK | 15-0 | SPARE | D04667J | | 18 | | | | | D05435P | 4 | | ALL |
| 015 | 24 | | PK | 15-0 | 34-12-22 | D04667J | | 19 | | | | | D05435P | 5 | | ALL |
| 016 | 24 | | PK | 15-0 | 34-12-22 | D04667J | | 20 | | | | | D05435P | 6 | | ALL |
| 018 | 22 | | PA | 15-0 | 31-31-11 | D04667J | | 12 | | | | | D05435P | 7 | | ALL |
| 022 | 24 | | PK | 15-0 | 34-61-24 | D04667J | | 1 | | | | | D05435P | 21 | | ALL |
| 023 | 24 | | PK | 15-0 | 34-53-21 | D04667J | | 2 | | | | | D05435P | 22 | | ALL |
| 024 | 22 | | PA | 15-0 | 31-31-11 | D04667J | | 4 | | | | | D05435P | 24 | | ALL |
| 025 | 22 | | PA | 15-0 | 31-31-11 | D04667J | | 5 | | | | | D05435P | 25 | | ALL |
| 029 | 24 | | PK | 15-0 | 31-31-12 | D05435P | | 39 | | | | | D05439J | 29 | | 150-199, 275-299 |
| 031 | 24 | | PK | 15-0 | 31-31-12 | D05435P | | 46 | | | | | D05439J | 31 | | 150-199, 275-299 |
| 033 | 24 | | PK | 15-0 | SPARE | D05435P | | 47 | | | | | D04667J | 49 | | ALL |
| 035 | 22 | | PA | 16-0 | 31-31-22 | D05499P | | 19 | | | | | D05439J | 9 | | ALL |
| 036 | 22 | | PA | 16-0 | 31-31-22 | D05499P | | 20 | | | | | D05439J | 10 | | ALL |
| 037 | 24 | | PK | 15-0 | 31-31-12 | D04667J | | 10 | | | | | D05435P | 30 | | ALL |
| 038 | 24 | | PK | 15-0 | 31-31-12 | D04667J | | 11 | | | | | D05435P | 31 | | ALL |
| 039 | 22 | | PA | 15-0 | SPARE | D04667J | | 44 | | | | | D05435P | 23 | | ALL |
| 040 | 24 | | PK | 15-0 | 34-55-21 | D04667J | | 37 | | | | | D05435P | 37 | | ALL |
| 043 | 24 | | PK | 15-0 | SPARE | D05435P | | 8 | | | | | D04667J | 45 | | ALL |
| 046 | 24 | | PK | 16-0 | 31-31-22 | D05435P | | 32 | | | | | D05439J | 2 | | ALL |
| 050 | 24 | | PK | 15-0 | 31-31-11 | D05435P | | 1 | | | | | D04667J | 30 | | ALL |
| 051 | 24 | | PK | 15-0 | 31-31-11 | D05435P | | 2 | | | | | D04667J | 31 | | ALL |
| 054 | 24 | | PK | 15-0 | 31-51-21 | D04667J | | 3 | | | | | D05435P | 11 | | ALL |
| 055 | 24 | | PK | 15-0 | 31-51-33 | D04667J | | 22 | | | | | D05435P | 12 | | ALL |
| 056 | 22 | | PA | 15-0 | SPARE | D05439J | | 17 | | | | | D05435P | 54 | | ALL |
| 057 | 22 | | PA | 15-0 | SPARE | D05439J | | 18 | | | | | D05435P | 55 | | ALL |
| 061 | 20 | | PQ | 15-0 | 27-32-31 | D05435P | | 48 | | | | | D04667J | 48 | | ALL |
| 061Z | | | | 0-0 | 27-32-31 | D05435P | | DED | | | | | D04667J | DED | | ALL |
| 062 | 24 | | PK | 16-0 | 34-61-25 | D05499P | | 1 | | | | | D05439J | 1 | | ALL |
| 063 | 24 | | PK | 16-0 | SPARE | D05499P | | 11 | | | | | D05439J | 21 | | 050-099 |
| 075 | 24 | | PK | 16-0 | 34-61-25 | D05439J | | 8 | | | | | D05499P | 11 | | 150-199, 275-299 |
| 203B | 24 | | PW | 15-0 | 31-31-12 | D04667J | | 8 | | | | | D05435P | 28 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0470

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0473 | 286T0473 | | | P37 TO E2-3 SHELF (continued) | | | | | | | | | | | |
| 203R | 24 | PW | IC | 0-0 | 31-31-12 | D04667J | | 9 | | D05435P | 29 | | | ALL | |
| 203Z | | | IC | 0-0 | 31-31-12 | D04667J | | 36 | | D05435P | 36 | | | ALL | |
| 210B | 24 | PW | IJ | 15-0 | 32-42-11 | D04667J | | 25 | | D05435P | 41 | | | ALL | |
| 210R | 24 | PW | IJ | 0-0 | 32-42-11 | D04667J | | 24 | | D05435P | 40 | | | ALL | |
| 210Z | | | IJ | 0-0 | 32-42-11 | D04667J | | 26 | | D05435P | 42 | | | ALL | |
| 214B | 24 | PW | IN | 15-0 | 31-31-12 | D05435P | | 34 | | D05439J | 24 | | | 150-199, 275-299 | |
| 214R | 24 | PW | IN | 0-0 | 31-31-12 | D05435P | | 33 | | D05439J | 23 | | | 150-199, 275-299 | |
| 214Z | | | IN | 0-0 | 31-31-12 | D05435P | | 35 | | D05439J | 25 | | | 150-199, 275-299 | |
| 215B | 24 | PW | IO | 15-0 | 27-32-21 | D05435P | | 50 | | D04667J | 43 | | | ALL | |
| 215R | 24 | PW | IO | 0-0 | 27-32-21 | D05435P | | 49 | | D04667J | 42 | | | ALL | |
| 215Z | | | IO | 0-0 | 27-32-21 | D05435P | | 44 | | D04667J | 41 | | | ALL | |
| 216B | 24 | PW | IP | 15-0 | 31-31-12 | D05435P | | 52 | | D05439J | 27 | | | 150-199, 275-299 | |
| 216R | 24 | PW | IP | 0-0 | 31-31-12 | D05435P | | 51 | | D05439J | 26 | | | 150-199, 275-299 | |
| 216Z | | | IP | 0-0 | 31-31-12 | D05435P | | 53 | | D05439J | 28 | | | 150-199, 275-299 | |
| 217B | 24 | PW | IQ | 16-0 | 34-61-25 | D05499P | | 2 | | D05439J | 3 | | | ALL | |
| 217R | 24 | PW | IQ | 0-0 | 34-61-25 | D05499P | | 3 | | D05439J | 4 | | | ALL | |
| 217Z | | | IQ | 0-0 | 34-61-25 | D05499P | | 4 | | D05439J | 5 | | | ALL | |
| 218B | 24 | PW | IR | 16-0 | 34-61-25 | D05499P | | 5 | | D05439J | 12 | | | ALL | |
| 218R | 24 | PW | IR | 0-0 | 34-61-25 | D05499P | | 6 | | D05439J | 13 | | | ALL | |
| 218Z | | | IR | 0-0 | 34-61-25 | D05499P | | 7 | | D05439J | 14 | | | ALL | |
| 219B | 24 | PW | IS | 16-0 | 34-61-25 | D05499P | | 8 | | D05439J | 15 | | | ALL | |
| 219R | 24 | PW | IS | 0-0 | 34-61-25 | D05499P | | 9 | | D05439J | 16 | | | ALL | |
| 219Z | | | IS | 0-0 | 34-61-25 | D05499P | | 10 | | D05439J | 20 | | | ALL | |
| 220B | 24 | PW | IT | 16-0 | SPARE | D04667J | | 51 | | D05499P | 21 | | | 150-199 | |
| 220R | 24 | PW | IT | 0-0 | SPARE | D04667J | | 50 | | D05499P | 22 | | | 150-199 | |
| 220Z | | | IT | 0-0 | SPARE | D04667J | | 52 | | D05499P | 23 | | | 150-199 | |
| 221B | 24 | PW | IU | 16-0 | SPARE | D04667J | | 54 | | D05499P | 14 | | | 150-199 | |
| 221R | 24 | PW | IU | 0-0 | SPARE | D04667J | | 53 | | D05499P | 13 | | | 150-199 | |
| 221Z | | | IU | 0-0 | SPARE | D04667J | | 55 | | D05499P | 15 | | | 150-199 | |
| 230B | 24 | PW | JE | 15-0 | 31-35-15 | D04667J | | 34 | | D05435P | 19 | | | 050-099, 150-199, 275-276, 278-299 | |
| 230R | 24 | PW | JE | 0-0 | 31-35-15 | D04667J | | 33 | | D05435P | 18 | | | 050-099, 150-199, 275-276, 278-299 | |
| 230Z | | | JE | 0-0 | 31-35-15 | D04667J | | 35 | | D05435P | 20 | | | 050-099, 150-199, 275-276, 278-299 | |
| 904B | 24 | PW | AA | 0-0 | 34-53-21 | D04667J | | 39 | | D05499P | 13 | | | 275-299 | |
| 904R | 24 | PW | AA | 10-0 | 34-53-21 | D04667J | | 38 | | D05499P | 12 | | | 275-299 | |
| 904Z | | | AA | 0-0 | 34-53-21 | D04667J | | 40 | | D05499P | 14 | | | 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0470

Page 10

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0474 | 286T0474 | | | R WING FRONT SPAR-R1-FLT CONT | | | | | | | | | | | | |
| 001 | 20 | | UA | 8-6 | 27-81-11 | D04422P | | | | 1 | | | D01524 | 1 | | ALL |
| 002 | 20 | | UA | 8-6 | 27-81-11 | D04422P | | | | 2 | | | D01524 | 2 | | ALL |
| 003 | 20 | | UA | 8-6 | 27-81-11 | D04422P | | | | 3 | | | D01524 | 3 | | ALL |
| 004 | 18 | | UA | 8-6 | 27-81-11 | D04422P | | | | 4 | | | D01524 | 7 | | ALL |
| 005 | 18 | | UA | 1-6 | 27-81-11 | GD03424 | | | | D.. | N | | D01524 | 6 | | ALL |
| 006 | 18 | | UA | 1-6 | 27-81-11 | GD03426 | | | | A.. | N | | D01524 | 5 | | ALL |
| 007 | 18 | | UA | 1-5 | 27-81-11 | GD03428 | | | | S.. | N | | D01524 | 8 | | ALL |
| W0475 | 286T0475 | | | P37 TO P33,E1-3 AND E1-5 SHELF | | | | | | | | | | | | |
| 001 | 22 | | PA | 23-0 | 22-14-31 | D05437P | | | | 1 | | | D04793J | 1 | | ALL |
| 002 | 22 | | PA | 23-0 | 22-14-31 | D05437P | | | | 2 | | | D04793J | 2 | | ALL |
| 003 | 24 | | PK | 23-0 | 31-51-41 | D05437P | | | | 3 | | | D04793J | 4 | | ALL |
| 005 | 24 | | PK | 23-0 | 27-32-21 | D05437P | | | | 5 | | | D04793J | 6 | | ALL |
| 006 | 24 | | PK | 21-0 | 77-35-11 | D05437P | | | | 6 | | | D05821J | 7 | | 050-099, 150-199 |
| 006 | 24 | | PK | 21-0 | 77-35-11 | D05821J | | | | 7 | | | D05437P | 6 | | 275-299 |
| 007 | 24 | | PK | 21-0 | 34-12-22 | D05437P | | | | 7 | | | D05821J | 12 | | ALL |
| 008 | 24 | | PK | 23-0 | SPARE | D05437P | | | | 8 | | | D04793J | 15 | | ALL |
| 011 | 24 | | PK | 34-0 | 22-41-11 | D04803P | | | | 4 | | | D04793J | 12 | | ALL |
| 012 | 20 | | PA | 23-0 | 38-32-11 | D05437P | | | | 12 | | | D04793J | 7 | | 050-099, 150-199, 277-299 |
| 012 | 22 | | PA | 23-0 | SPARE | D05437P | | | | 12 | | | D04793J | 7 | | 275 |
| 012 | 20 | | PA | 23-0 | SPARE | D05437P | | | | 12 | | | D04793J | 7 | | 276 |
| 013 | 22 | | PA | 21-0 | SPARE | D05437P | | | | 13 | | | D05821J | 14 | | ALL |
| 014 | 24 | | PK | 21-0 | SPARE | D05437P | | | | 14 | | | D05821J | 15 | | ALL |
| 015 | 24 | | PK | 21-0 | 34-31-31 | D05437P | | | | 15 | | | D05821J | 16 | | ALL |
| 016 | 24 | | PK | 32-0 | 77-35-11 | D04803P | | | | 1 | | | D05821J | 1 | | ALL |
| 017 | 24 | | PK | 14-3 | 34-12-22 | D04803P | | | | 3 | | | D05437P | 16 | | ALL |
| 018 | 24 | | PK | 32-0 | SPARE | D04803P | | | | 2 | | | D05821J | 10 | | ALL |
| 019 | 24 | | PK | 34-0 | SPARE | D04803P | | | | 7 | | | D04793J | 9 | | ALL |
| 020 | 24 | | PK | 14-3 | SPARE | D04803P | | | | 8 | | | D05437P | 32 | | ALL |
| 021 | 24 | | PK | 14-3 | 34-12-22 | D04803P | | | | 9 | | | D05437P | 33 | | ALL |
| 022 | 24 | | PK | 14-3 | 34-12-22 | D04803P | | | | 10 | | | D05437P | 34 | | ALL |
| 023 | 24 | | PK | 14-3 | SPARE | D04803P | | | | 11 | | | D05437P | 35 | | ALL |
| 024 | 24 | | PK | 14-3 | SPARE | D04803P | | | | 12 | | | D05437P | 36 | | ALL |
| 025 | 24 | | PK | 21-0 | SPARE | D05821J | | | | 21 | | | D05437P | 37 | | ALL |
| 026 | 24 | | PK | 34-0 | 33-16-14 | D04803P | | | | 14 | | | D04793J | 16 | | ALL |
| 064 | 22 | | PA | 23-0 | 34-22-26 | D05437P | | | | 4 | | | D04793J | 14 | | ALL |
| 201B | 24 | | PW IA | 21-0 | 31-31-12 | D05437P | | | | 21 | | | D05821J | 3 | | ALL |
| 201R | 24 | | PW IA | 0-0 | 31-31-12 | D05437P | | | | 20 | | | D05821J | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0470

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|--------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0475 | 286T0475 | | | P37 TO P33,E1-3 AND E1-5 SHELF (continued) | | | | | | | | | | | | |
| 201Z | | | IA | 0-0 | 31-31-12 | D05437P | | 22 | | | D05821J | | 8 | | ALL | |
| 202B | 24 | | PW | IB | 21-0 | 31-31-12 | D05437P | | 24 | | D05821J | | 18 | | ALL | |
| 202R | 24 | | PW | IB | 0-0 | 31-31-12 | D05437P | | 23 | | D05821J | | 17 | | ALL | |
| 202Z | | | | IB | 0-0 | 31-31-12 | D05437P | | 25 | | D05821J | | 19 | | ALL | |
| 203B | 24 | | PW | IC | 21-0 | 31-31-12 | D05437P | | 27 | | D05821J | | 23 | | 150-199, 275-299 | |
| 203R | 24 | | PW | IC | 0-0 | 31-31-12 | D05437P | | 26 | | D05821J | | 22 | | 150-199, 275-299 | |
| 203Z | | | | IC | 0-0 | 31-31-12 | D05437P | | 28 | | D05821J | | 24 | | 150-199, 275-299 | |
| 204B | 24 | | PW | ID | 21-0 | 73-21-14 | D05437P | | 30 | | D05821J | | 5 | | ALL | |
| 204R | 24 | | PW | ID | 0-0 | 73-21-14 | D05437P | | 29 | | D05821J | | 4 | | ALL | |
| 204Z | | | | ID | 0-0 | 73-21-14 | D05437P | | 31 | | D05821J | | 6 | | ALL | |
| 205B | 24 | | PW | IE | 21-0 | SPARE | D05437P | | 10 | | D05821J | | 26 | | 050-099, 150-199 | |
| 205R | 24 | | PW | IE | 0-0 | SPARE | D05437P | | 9 | | D05821J | | 25 | | 050-099, 150-199 | |
| 205Z | | | | IE | 0-0 | SPARE | D05437P | | 11 | | D05821J | | 27 | | 050-099, 150-199 | |
| 70K | 20 | | PA | | 34-0 | 29-11-14 | D04803P | | 15 | | D04793J | | 24 | | ALL | |
| 70M | 20 | | PA | | 34-0 | 29-11-14 | D04803P | | 13 | | D04793J | | 23 | | ALL | |
| W0476 | 286T0476 | | | R WING REAR SPAR-L1-FUEL BOOST PMP | | | | | | | | | | | | |
| 001 | 18 | | UA | | 9-1 | 28-22-11 | GD03436 | | S.. | N | D03986 | | 3 | | ALL | |
| 301B | 18 | | VH | A | 24-1 | 28-22-11 | D05512P | | 2 | | D03986 | | 2 | | ALL | |
| 301R | 18 | | VH | A | 0-0 | 28-22-11 | D05512P | | 3 | | D03986 | | 4 | | ALL | |
| 301Y | 18 | | VH | A | 0-0 | 28-22-11 | D05512P | | 4 | | D03986 | | 6 | | ALL | |
| 301Z | | | | A | 0-0 | 28-22-11 | GD03972 | | S.. | N | GD04042 | | S.. | N | ALL | |
| W0478 | 286T0478 | | | R WING REAR SPAR-R1-FUEL BOOST PMP | | | | | | | | | | | | |
| 001 | 14 | | UA | | 9-5 | 28-22-12 | GD03438 | | S.. | N | *1 | D02804 | | 3 | 050-099, 155-199, 276-299 | |
| 001 | 14 | | UA | | 9-5 | 28-22-12 | GD03438 | | S.. | N | | D02804 | | 3 | 150-154, 275 | |
| 002 | 18 | | UA | | 13-11 | 28-22-11 | GD03438 | | S.. | N | *1 | D01540 | | 3 | 050-099, 155-199, 276-299 | |
| 002 | 18 | | UA | | 13-11 | 28-22-11 | GD03438 | | S.. | N | | D01540 | | 3 | 150-154, 275 | |
| 006 | 14 | | UA | | 9-4 | 28-31-21 | D12190 | | 3 | | GD04108 | | S.. | N | 155-157, 165-199, 277-299 | |
| 300B | 14 | | OC | LY | 23-6 | 28-31-21 | D05508P | | 4 | | D12190 | | 6 | | 155-157, 165-199, 277-299 | |
| 300R | 14 | | OC | LY | 0-0 | 28-31-21 | D05508P | | 5 | | D12190 | | 4 | | 155-157, 165-199, 277-299 | |
| 300Y | 14 | | OC | LY | 0-0 | 28-31-21 | D05508P | | 6 | | D12190 | | 2 | | 155-157, 165-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W0470
Page 12
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0478 | 286T0478 | | | | R WING REAR SPAR-R1-FUEL BOOST PMP (continued) | | | | | | | | | | |
| 300Z | | | | LY | 0-0 | 28-31-21 | GD04040 | S.. | N | | GD04058 | S.. | N | | 155-157, 165-199, 277-299 |
| 301B | 14 | OC | A | | 23-11 | 28-22-12 | D05508P | 1 | | | D02804 | 2 | | | ALL |
| 301R | 14 | OC | A | | 0-0 | 28-22-12 | D05508P | 2 | | | D02804 | 4 | | | ALL |
| 301Y | 14 | OC | A | | 0-0 | 28-22-12 | D05508P | 3 | | | D02804 | 6 | | | ALL |
| 301Z | | | A | | 0-0 | 28-22-12 | GD04040 | S.. | N | | GD04058 | S.. | N | | ALL |
| 302B | 18 | VH | B | | 26-8 | 28-22-11 | D04410P | 1 | | | D01540 | 2 | | | ALL |
| 302R | 18 | VH | B | | 0-0 | 28-22-11 | D04410P | 2 | | | D01540 | 4 | | | ALL |
| 302Y | 18 | VH | B | | 0-0 | 28-22-11 | D04410P | 3 | | | D01540 | 6 | | | ALL |
| 302Z | | | B | | 0-0 | 28-22-11 | GD04040 | S.. | N | | GD04042 | S.. | N | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0480 | 286T0480 | | | R WING OUTBD FS-L2-FLIGHT CONTROLS | | | | | | | | | | | | | |
| 001 | 18 | | UA | | 1-5 | 27-88-22 | D04378J | | 15 | | | | SM00001 | | 9 | | ALL |
| 002 | 18 | | UA | | 1-5 | 27-88-22 | D04378J | | 17 | | | | SM00002 | | 9 | | ALL |
| 003 | 18 | | UA | | 1-5 | 27-88-22 | D04378J | | 21 | | | | SM00003 | | 9 | | ALL |
| 004 | 18 | | UA | | 1-5 | 27-88-22 | D04378J | | 3 | | | | SM00004 | | 9 | | ALL |
| 005 | 18 | | UA | | 1-5 | 27-88-22 | D04378J | | 9 | | | | SM00005 | | 9 | | ALL |
| 006 | 18 | | UA | | 1-5 | 27-88-22 | D04378J | | 1 | | | | SM00006 | | 9 | | ALL |
| 007 | 18 | | UA | | 1-5 | 27-88-22 | D04378J | | 5 | | | | SM00007 | | 9 | | ALL |
| 008 | 18 | | UA | | 1-5 | 27-88-22 | D04378J | | 7 | | | | SM00008 | | 9 | | ALL |
| 009 | 18 | | UA | | 1-5 | 27-88-22 | D04378J | | 11 | | | | SM00009 | | 9 | | ALL |
| 010 | 18 | | UA | | 1-5 | 27-88-22 | D04378J | | 13 | | | | SM00010 | | 9 | | ALL |
| 01TB | 20 | | ZZ | H | 9-0 | 27-88-22 | SM00001 | | | 9 | | | SP00178 | | 9 | | ALL |
| 01TI | | | | H | 0-0 | 27-88-22 | SM00001 | | | 9 | | | SP00180 | DED | | | ALL |
| 01TO | | | | H | 0-0 | 27-88-22 | GD03516 | | S.. | N | *1 | | GD03708 | S.. | N | | ALL |
| 01TR | 20 | | ZZ | H | 0-0 | 27-88-22 | D04378J | | 16 | | | | SP00180 | | 9 | | ALL |
| 02TB | 20 | | ZZ | J | 5-0 | 27-88-22 | SM00002 | | | 9 | | | SP00182 | | 9 | | ALL |
| 02TI | | | | J | 0-0 | 27-88-22 | SM00002 | | | 9 | | | SP00184 | DED | | | ALL |
| 02TO | | | | J | 0-0 | 27-88-22 | GD03516 | | S.. | N | *1 | | GD03754 | S.. | N | | ALL |
| 02TR | 20 | | ZZ | J | 0-0 | 27-88-22 | D04378J | | 18 | | | | SP00184 | | 9 | | ALL |
| 03TB | 20 | | ZZ | L | 21-0 | 27-88-22 | SM00003 | | | 9 | | | SP00190 | | 9 | | ALL |
| 03TI | | | | L | 0-0 | 27-88-22 | SM00003 | | | 9 | | | SP00192 | DED | | | ALL |
| 03TO | | | | L | 0-0 | 27-88-22 | GD03516 | | S.. | N | *1 | | GD03712 | S.. | N | | ALL |
| 03TR | 20 | | ZZ | L | 0-0 | 27-88-22 | D04378J | | 22 | | | | SP00192 | | 9 | | ALL |
| 04TB | 20 | | ZZ | M | 17-0 | 27-88-22 | SM00004 | | | 9 | | | SP00194 | | 9 | | ALL |
| 04TI | | | | M | 0-0 | 27-88-22 | SM00004 | | | 9 | | | SP00196 | DED | | | ALL |
| 04TO | | | | M | 0-0 | 27-88-22 | GD03516 | | S.. | N | *1 | | GD03750 | S.. | N | | ALL |
| 04TR | 20 | | ZZ | M | 0-0 | 27-88-22 | D04378J | | 4 | | | | SP00196 | | 9 | | ALL |
| 05TB | 20 | | ZZ | P | 35-0 | 27-88-22 | SM00005 | | | 9 | | | SP00202 | | 9 | | ALL |
| 05TI | | | | P | 0-0 | 27-88-22 | SM00005 | | | 9 | | | SP00204 | DED | | | ALL |
| 05TO | | | | P | 0-0 | 27-88-22 | GD03516 | | S.. | N | *2 | | GD03716 | S.. | N | | ALL |
| 05TR | 20 | | ZZ | P | 0-0 | 27-88-22 | D04378J | | 10 | | | | SP00204 | | 9 | | ALL |
| 06TB | 20 | | ZZ | A | 31-0 | 27-88-22 | SM00006 | | | 9 | | | SP00206 | | 9 | | ALL |
| 06TI | | | | A | 0-0 | 27-88-22 | SM00006 | | | 9 | | | SP00208 | DED | | | ALL |
| 06TO | | | | A | 0-0 | 27-88-22 | GD03516 | | S.. | N | *2 | | GD03758 | S.. | N | | ALL |
| 06TR | 20 | | ZZ | A | 0-0 | 27-88-22 | D04378J | | 2 | | | | SP00208 | | 9 | | ALL |
| 07TB | 20 | | ZZ | C | 48-0 | 27-88-22 | SM00007 | | | 9 | | | SP00214 | | 9 | | ALL |
| 07TI | | | | C | 0-0 | 27-88-22 | SM00007 | | | 9 | | | SP00216 | DED | | | ALL |
| 07TO | | | | C | 0-0 | 27-88-22 | GD03516 | | S.. | N | *2 | | GD03720 | S.. | N | | ALL |
| 07TR | 20 | | ZZ | C | 0-0 | 27-88-22 | D04378J | | 6 | | | | SP00216 | | 9 | | ALL |
| 08TB | 20 | | ZZ | D | 43-0 | 27-88-22 | SM00008 | | | 9 | | | SP00218 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0480
 Page 1
 Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0480 | 286T0480 | | | R WING OUTBD FS-L2-FLIGHT CONTROLS (continued) | | | | | | | | | | | | |
| 08TI | | | D | 0-0 | 27-88-22 | SM00008 | | 9 | | | SP00220 | DED | | | ALL | |
| 08TO | | | D | 0-0 | 27-88-22 | GD03516 | | S.. | N | *3 | GD03760 | S.. | N | | ALL | |
| 08TR | 20 | 2Z | D | 0-0 | 27-88-22 | D04378J | | 8 | | | SP00220 | | 9 | | ALL | |
| 09TB | 20 | 2Z | F | 61-0 | 27-88-22 | SM00009 | | 9 | | | SP00226 | | 9 | | ALL | |
| 09TI | | | F | 0-0 | 27-88-22 | SM00009 | | 9 | | | SP00228 | DED | | | ALL | |
| 09TO | | | F | 0-0 | 27-88-22 | GD03516 | | S.. | N | *3 | GD03724 | S.. | N | | ALL | |
| 09TR | 20 | 2Z | F | 0-0 | 27-88-22 | D04378J | | 12 | | | SP00228 | | 9 | | ALL | |
| 10TB | 20 | 2Z | G | 56-0 | 27-88-22 | SM00010 | | 9 | | | SP00230 | | 9 | | ALL | |
| 10TI | | | G | 0-0 | 27-88-22 | SM00010 | | 9 | | | SP00232 | DED | | | ALL | |
| 10TO | | | G | 0-0 | 27-88-22 | GD03516 | | S.. | N | *3 | GD03762 | S.. | N | | ALL | |
| 10TR | 20 | 2Z | G | 0-0 | 27-88-22 | D04378J | | 14 | | | SP00232 | | 9 | | ALL | |
| 216B | 18 | UB | B | 65-0 | 27-89-11 | D04378J | | 19 | | | D07550J | | 2 | | ALL | |
| 216R | 18 | UB | B | 0-0 | 27-89-11 | D04378J | | 20 | | | D07550J | | 1 | | ALL | |
| A-A | | | S | 0-0 | 27-88-22 | S00298 | | BLU | | | SP00178 | | 9 | | ALL | |
| A-B | | | S | 0-0 | 27-88-22 | S00298 | | RED | | | SP00180 | | 9 | | ALL | |
| A-C | | | T | 0-0 | 27-88-22 | S00304 | | BLU | | | SP00182 | | 9 | | ALL | |
| A-D | | | T | 0-0 | 27-88-22 | S00304 | | RED | | | SP00184 | | 9 | | ALL | |
| A-G | | | V | 0-0 | 27-88-22 | S00297 | | BLU | | | SP00190 | | 9 | | ALL | |
| A-H | | | V | 0-0 | 27-88-22 | S00297 | | RED | | | SP00192 | | 9 | | ALL | |
| A-J | | | W | 0-0 | 27-88-22 | S00303 | | BLU | | | SP00194 | | 9 | | ALL | |
| A-K | | | W | 0-0 | 27-88-22 | S00303 | | RED | | | SP00196 | | 9 | | ALL | |
| A-N | | | Y | 0-0 | 27-88-22 | S00296 | | BLU | | | SP00202 | | 9 | | ALL | |
| A-P | | | Y | 0-0 | 27-88-22 | S00296 | | RED | | | SP00204 | | 9 | | ALL | |
| A-Q | | | Z | 0-0 | 27-88-22 | S00302 | | BLU | | | SP00206 | | 9 | | ALL | |
| A-R | | | Z | 0-0 | 27-88-22 | S00302 | | RED | | | SP00208 | | 9 | | ALL | |
| A-U | | | AB | 0-0 | 27-88-22 | S00295 | | BLU | | | SP00214 | | 9 | | ALL | |
| A-V | | | AB | 0-0 | 27-88-22 | S00295 | | RED | | | SP00216 | | 9 | | ALL | |
| A-W | | | AC | 0-0 | 27-88-22 | S00301 | | BLU | | | SP00218 | | 9 | | ALL | |
| A-X | | | AC | 0-0 | 27-88-22 | S00301 | | RED | | | SP00220 | | 9 | | ALL | |
| B-A | | | AE | 0-0 | 27-88-22 | S00294 | | BLU | | | SP00226 | | 9 | | ALL | |
| B-B | | | AE | 0-0 | 27-88-22 | S00294 | | RED | | | SP00228 | | 9 | | ALL | |
| B-C | | | AF | 0-0 | 27-88-22 | S00300 | | BLU | | | SP00230 | | 9 | | ALL | |
| B-D | | | AF | 0-0 | 27-88-22 | S00300 | | RED | | | SP00232 | | 9 | | ALL | |
| W0481 | 286T0481 | | | ILS-L,SHELF TO CONT PNL | | | | | | | | | | | | |
| 001 | 20 | PA | | 25-2 | 34-31-11 | D04365J | | 5 | | | D00155 | | 5 | | ALL | |
| 002 | 20 | PA | | 1-6 | 34-31-11 | GD04474 | | S.. | 2 | | D00155 | | 7 | | ALL | |
| 003 | 22 | PA | | 25-2 | 34-31-11 | D04365J | | 11 | | | D00155 | | 11 | | ALL | |
| 004 | 22 | PA | | 29-9 | 22-11-12 | D04365J | | 30 | | | TB0307F | A002 | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0480

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0481 | 286T0481 | | | ILS-L,SHELF TO CONT PNL (continued) | | | | | | | | | | | |
| 004Y | 22 | | PJ | | 18-10 | 27-41-11 | SP00437 | | | 9 | D04365J | | 49 | | 050-099 |
| 005 | 22 | | PA | | 29-9 | 22-11-12 | D04365J | | 10 | | TB0307F | C002 | 2 | | ALL |
| 006 | 22 | | PA | | 29-9 | 22-11-12 | D04365J | | 46 | | TB0307F | A003 | 2 | | ALL |
| 006Y | 22 | | PJ | | 20-2 | 27-41-11 | SP00405 | | | 9 | D04365J | | 2 | | 050-099, 275-299 |
| 007 | 22 | | PA | | 7-1 | 22-11-12 | TB0207F | C003 | 2 | | TB0307F | C003 | 2 | | ALL |
| 008 | 22 | | PA | | 25-8 | 22-11-12 | D04365J | | 25 | | TB0207F | A003 | 2 | | ALL |
| 009 | 22 | | PA | | 25-8 | 22-11-12 | D04365J | | 15 | | TB0207F | C002 | 2 | | ALL |
| 010 | 22 | | PA | | 25-8 | 22-11-12 | D04365J | | 4 | | TB0207F | A002 | 2 | | ALL |
| 011 | 24 | | PK | | 28-2 | SPARE | D04551P | | 11 | | D04365J | | 31 | | ALL |
| 013 | 20 | | PA | | 27-5 | 22-31-11 | D04365J | | 16 | | D00203 | | Y | | ALL |
| 014 | 24 | | PK | | 27-5 | 22-31-11 | D04365J | | 17 | | D00203 | | X | | ALL |
| 015 | 20 | | PA | | 13-9 | 22-31-11 | GD00589 | A.. | 2 | | D00203 | | Z | | ALL |
| 016 | 20 | | PA | | 13-9 | 22-31-11 | GD00589 | S.. | 2 | | D00203 | | A- | | ALL |
| 017 | 24 | | PK | | 28-2 | 22-32-15 | D04365J | | 3 | | D04551P | | 3 | | ALL |
| 018 | 24 | | PK | | 28-2 | 22-32-15 | D04365J | | 34 | | D04551P | | 4 | | ALL |
| 019 | 24 | | PK | | 28-2 | 22-32-15 | D04365J | | 35 | | D04551P | | 5 | | ALL |
| 020 | 24 | | PK | | 28-2 | SPARE | D04365J | | 6 | | D04551P | | 6 | | 050-099 |
| 021 | 24 | | PK | | 28-2 | SPARE | D04365J | | 7 | | D04551P | | 7 | | 050-099 |
| 022 | 24 | | PK | | 28-2 | SPARE | D04365J | | 38 | | D04551P | | 8 | | 050-099 |
| 023 | 22 | | PA | | 28-2 | SPARE | D04365J | | 39 | | D04551P | | 9 | | ALL |
| 024 | 24 | | PK | | 28-2 | SPARE | D04365J | | 40 | | D04551P | | 10 | | 050-099, 275-299 |
| 024 | 24 | | PK | | 28-2 | 31-31-15 | D04365J | | 40 | | D04551P | | 10 | | 150-154 |
| 025 | 24 | | PK | | 28-2 | SPARE | D04551P | | 17 | | D04365J | | 49 | | 150-199, 275-299 |
| 026 | 20 | | PA | | 28-2 | 27-41-11 | D04365J | | 33 | | D04551P | | 1 | | ALL |
| 027 | 20 | | PA | | 28-2 | 27-41-11 | D04365J | | 28 | | D04551P | | 2 | | ALL |
| 028 | 24 | | PK | | 29-2 | 27-48-11 | D04365J | | 21 | | D02236 | | 8 | | 050-099, 150-154, 157-164, 167-199, 275-299 |
| 029 | 24 | | PK | | 29-2 | 27-48-11 | D04365J | | 36 | | D02236 | | 7 | | 050-099, 150-154, 157-164, 167-199, 275-299 |
| 030 | 24 | | PK | | 29-2 | 27-48-11 | D04365J | | 37 | | D02236 | | 6 | | 050-099, 150-154, 157-164, 167-199, 275-299 |
| 031 | 22 | | PA | | 28-2 | 22-12-11 | D04365J | | 41 | | D04551P | | 21 | | ALL |
| 032 | 22 | | PA | | 28-2 | 22-12-11 | D04365J | | 42 | | D04551P | | 22 | | ALL |
| 033 | 22 | | PA | | 28-2 | 22-12-11 | D04365J | | 43 | | D04551P | | 23 | | ALL |
| 034 | 24 | | PK | | 28-2 | 31-51-42 | D04365J | | 48 | | D04551P | | 18 | | ALL |
| 035 | 24 | | PK | | 28-2 | 22-32-13 | D04365J | | 22 | | D04551P | | 12 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0480
Page 3
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|--|-------|-------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0481 | 286T0481 | ILS-L,SHELF TO CONT PNL (continued) | | | | | | | | | | | | | | | |
| 036 | 24 | | PK | 28-2 | 22-32-13 | D04365J | 23 | | | | | | D04551P | 13 | | | ALL |
| 037 | 24 | | PK | 28-2 | 22-32-13 | D04365J | 24 | | | | | | D04551P | 14 | | | ALL |
| 038 | 20 | | PA | 1-0 | 22-32-13 | SM00001 | | | | | S | | D00203 | C | | | ALL |
| 039 | 20 | | PA | 1-0 | 22-32-13 | SM00001 | | | | | S | | D00203 | B | | | ALL |
| 040 | 20 | | PA | 13-9 | 22-31-11 | D00203 | | B- | | | | | GD00589 | A.. | 2 | | ALL |
| 043 | 20 | | PA | 1-3 | 27-48-11 | D02236 | | 3 | | | | | GD00605 | S.. | E | | ALL |
| 044 | 20 | | PA | 2-7 | 27-48-11 | D02236 | | 9 | | | | | GD00603 | A.. | 2 | | ALL |
| 045 | 20 | | PA | 13-0 | 33-13-18 | D02236 | | 1 | | | | | SP02288 | | 9 | | ALL |
| 046 | 20 | | PA | 2-7 | 33-13-18 | D02236 | | 2 | | | | | GD00603 | A.. | 2 | | ALL |
| 047 | 20 | | PA | 19-2 | 27-21-11 | D04365J | 45 | | | | | | TB0031F | A022 | 2 | | ALL |
| 050 | 24 | | PK | 28-2 | SPARE | D04551P | 15 | | | | | | D04365J | 2 | | | 150-199 |
| 051 | 22 | | PA | 28-2 | 27-41-11 | D04551P | 16 | | | | | | D04365J | 29 | | | 150-154 |
| 055 | 22 | | PA | 28-2 | SPARE | D04365J | 54 | | | | | | D04551P | 24 | | | 050-099, 150-199 |
| 060 | 22 | | PA | 19-2 | 31-51-33 | D04365J | 55 | | | | | | TB0031F | A023 | 2 | | ALL |
| 061 | 24 | | PK | 19-2 | 31-51-33 | D04365J | 50 | | | | | | TB0031Y | C003 | BJ | | ALL |
| 062 | 24 | | PK | 19-2 | 31-51-33 | D04365J | 51 | | | | | | TB0031Y | A003 | BJ | | ALL |
| 201B | 22 | | PB IA | 25-2 | 34-31-11 | D04365J | 8 | | | | | | D00155 | 8 | | | ALL |
| 201R | 22 | | PB IA | 0-0 | 34-31-11 | D04365J | 9 | | | | | | D00155 | 9 | | | ALL |
| 202B | 24 | | PW IB | 25-2 | 34-31-11 | D04365J | 13 | | | | | | D00155 | 13 | | | ALL |
| 202R | 24 | | PW IB | 0-0 | 34-31-11 | D04365J | 14 | | | | | | D00155 | 14 | | | ALL |
| 202Z | | | | 0-0 | 34-31-11 | D04365J | 12 | | | | | | D00155 | 12 | | | ALL |
| 205B | 24 | | PL IE | 27-5 | 22-32-13 | D04365J | 27 | | | | | | D00203 | M | | | ALL |
| 205R | 24 | | PL IE | 0-0 | 22-32-13 | D04365J | 26 | | | | | | D00203 | N | | | ALL |
| 206B | 22 | | PB IF | 28-2 | SPARE | D04551P | 20 | | | | | | D04365J | 53 | | | 050-099, 150-199 |
| 206R | 22 | | PB IF | 0-0 | SPARE | D04551P | 19 | | | | | | D04365J | 52 | | | 050-099, 150-199 |
| 301B | 20 | | PC MA | 27-5 | 22-32-13 | D04365J | 19 | | | | | | SM00001 | | S | | ALL |
| 301R | 20 | | PC MA | 0-0 | 22-32-13 | D04365J | 18 | | | | | | D00203 | D | | | ALL |
| 301Y | 20 | | PC MA | 0-0 | 22-32-13 | D04365J | 20 | | | | | | D00203 | A | | | ALL |
| 302B | 24 | | PM MB | 29-2 | 27-48-11 | D04365J | 36 | | | | | | D02236 | 7 | | | 155-156, 165-166 |
| 302R | 24 | | PM MB | 0-0 | 27-48-11 | D04365J | 37 | | | | | | D02236 | 6 | | | 155-156, 165-166 |
| 302Y | 24 | | PM MB | 0-0 | 27-48-11 | D04365J | 21 | | | | | | D02236 | 8 | | | 155-156, 165-166 |
| W0482 | 286T0482 | L WING REAR SPAR-S2C-FUEL | | | | | | | | | | | | | | | |
| 001 | 18 | | VF D | 16-1 | 28-25-21 | SP00462 | | | | | | 9 | D05698P | 7 | | | ALL |
| 001Z | | | | 0-0 | 28-25-21 | SP01950 | | | | | | 9 | GD04038 | S.. | N | | ALL |
| 007 | 18 | | UA | 2-5 | 28-21-13 | D02798 | | | | | 1 | DK | GD03442 | D.. | N | | ALL |
| 008 | 18 | | UA | 2-5 | 28-21-13 | D02798 | | | | | 4 | DK | GD03442 | D.. | N | | ALL |
| 009 | 18 | | UA | 1-3 | 28-21-13 | D02798 | | | | | 3 | DK | GD04606 | S.. | N | | ALL |
| 010 | 14 | | VF A | 17-10 | 28-25-11 | D01570 | | | | | 1 | | D05698P | 6 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0480

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0482 | 286T0482 | | | L WING REAR SPAR-S2C-FUEL (continued) | | | | | | | | | | | |
| 010Z | | | | A | 0-0 | 28-25-11 | GD04372 | S.. | N | | GD04038 | S.. | N | | ALL |
| 011 | 14 | | UA | | 2-11 | 28-25-11 | D01570 | 2 | | | GD03446 | D.. | N | | ALL |
| 012 | 14 | | UA | | 2-11 | 28-25-11 | D01570 | 3 | | | GD03448 | S.. | N | | ALL |
| 201B | 18 | | VG | B | 17-5 | 28-21-13 | D02798 | 2 | DK | | D05698P | 4 | | | ALL |
| 201R | 18 | | VG | B | 0-0 | 28-21-13 | D02798 | 5 | DK | | D05698P | 5 | | | ALL |
| 201Z | | | | B | 0-0 | 28-21-13 | GD04606 | S.. | N | | GD04038 | S.. | N | | ALL |
| W0483 | 286T0483 | | | ILS-C,SHELF TO CONT PANEL | | | | | | | | | | | |
| 001 | 22 | | PA | | 27-0 | 34-31-31 | D04409J | 5 | | | D00603 | 5 | | | ALL |
| 002 | 20 | | PA | | 1-6 | 34-31-31 | GD04472 | S.. | 2 | | D00603 | 7 | | | ALL |
| 003 | 22 | | PA | | 27-0 | 34-31-31 | D04409J | 11 | | | D00603 | 11 | | | ALL |
| 004 | 22 | | PA | | 32-0 | 22-11-32 | D04409J | 1 | | | TB0307F | A001 | 2 | | ALL |
| 005 | 22 | | PA | | 28-0 | 22-11-32 | D04409J | 2 | | | TB0207F | C001 | 2 | | ALL |
| 006 | 22 | | PA | | 8-0 | 22-11-32 | TB0207F | A001 | 2 | | TB0307F | C001 | 2 | | ALL |
| 007 | 22 | | PA | | 31-0 | 22-12-31 | D04553P | 3 | | | D04409J | 13 | | | ALL |
| 008 | 22 | | PA | | 31-0 | 22-12-31 | D04553P | 4 | | | D04409J | 14 | | | ALL |
| 009 | 22 | | PA | | 31-0 | 22-12-31 | D04553P | 5 | | | D04409J | 15 | | | ALL |
| 010 | 18 | | PA | | 4-0 | 33-13-18 | D00603 | 1 | DK | | SP02276 | | 9 | | 050-099, 150-155, 162-165, 275-276 |
| 011 | 20 | | PA | | 1-6 | 33-13-18 | D00603 | 2 | | | GD04456 | A.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 012 | 24 | | PK | | 31-0 | SPARE | D04409J | 10 | | | D04553P | 2 | | | ALL |
| 201B | 22 | | PB | IA | 27-0 | 34-31-31 | D04409J | 8 | | | D00603 | 8 | | | ALL |
| 201R | 22 | | PB | IA | 0-0 | 34-31-31 | D04409J | 9 | | | D00603 | 9 | | | ALL |
| 202B | 24 | | PW | IB | 27-0 | 34-31-31 | D04409J | 7 | | | D00603 | 13 | | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-31-31 | D04409J | 6 | | | D00603 | 14 | | | ALL |
| 202Z | | | | IB | 0-0 | 34-31-31 | D04409J | 12 | | | D00603 | 12 | | | ALL |
| 208B | 18 | | PB | IH | 4-0 | 33-13-18 | D00603 | 2 | DK | | SP05000 | | 9 | | 156-157, 166-199, 277-299 |
| 208R | 18 | | PB | IH | 0-0 | 33-13-18 | D00603 | 1 | DK | | SP02276 | | 9 | | 156-157, 166-199, 277-299 |
| W0484 | 286T0484 | | | L WING REAR SPAR-S2D-FUEL | | | | | | | | | | | |
| 002 | 20 | | VF | A | 2-5 | 28-25-21 | D01564 | 6 | | | SP00462 | | 9 | | 050-099, 150-156, 162-166, 275-276 |
| 002 | 20 | | VF | A | 2-6 | 28-25-21 | D01564 | 6 | | | SP00462 | | 9 | | 157, 167-199, 277-299 |
| 002Z | | | | A | 0-0 | 28-25-21 | GD04072 | S.. | N | | SP01950 | | 9 | | ALL |
| 003 | 18 | | UA | | 2-3 | 28-25-21 | D01564 | 4 | | | GD03450 | D.. | N | | 050-099, 150-156, 162-166, 275-276 |

WIRE LIST
D280T132

91-21-11
Section W0480
Page 5
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0484 | 286T0484 | | | L WING REAR SPAR-S2D-FUEL (continued) | | | | | | | | | | | | | |
| 003 | 18 | UA | | 2-6 | 28-25-21 | D01564 | 4 | | | | | | GD03450 | D.. | N | | 157, 167-199, 277-299 |
| 009 | 18 | UA | | 1-3 | 28-21-13 | D01618 | 3 | DK | | | | | GD03454 | S.. | N | | ALL |
| 010 | 20 | VF | C | 79-0 | 27-11-12 | D01634 | 3 | | | | | | D05700P | 2 | | | ALL |
| 010Z | | | C | 0-0 | 27-11-12 | GD03458 | S.. | N | | | | | GD03942 | S.. | N | | ALL |
| 011 | 18 | UA | | 1-8 | 27-11-12 | D01634 | 6 | | | | | | GD03458 | S.. | N | | ALL |
| 017 | 18 | UA | | 2-3 | 28-25-21 | D01564 | 7 | | | | | | GD03464 | S.. | N | | 050-099, 150-156, 162-166, 275-276 |
| 017 | 18 | UA | | 2-6 | 28-25-21 | D01564 | 7 | | | | | | GD03464 | S.. | N | | 157, 167-199, 277-299 |
| 021 | 20 | UA | | 1-5 | 31-31-22 | D05700P | | | | FA | | | GD00417 | S.. | N | | 050-099, 275-299 |
| 021 | 20 | UA | | 1-5 | 31-31-22 | GD00417 | S.. | N | | | | | D05700P | | | FA | 150-199 |
| 024 | 20 | VF | AX | 4-9 | 31-31-22 | D05700P | 1 | | | | | | D01923 | 1 | | | ALL |
| 024Z | | | AX | 0-0 | 31-31-22 | D05700P | DED | | | | | | D01923 | DED | | | ALL |
| 202B | 20 | VG | IB | 4-9 | 31-31-22 | D05700P | 7 | | | | | | D01923 | 3 | | | 050-099, 275-299 |
| 202B | 20 | VG | IB | 4-9 | 31-31-22 | D01923 | 3 | | | | | | D05700P | 7 | | | 150-199 |
| 202R | 20 | VG | IB | 0-0 | 31-31-22 | D05700P | 9 | | | | | | D01923 | 2 | | | 050-099, 275-299 |
| 202R | 20 | VG | IB | 0-0 | 31-31-22 | D01923 | 2 | | | | | | D05700P | 9 | | | 150-199 |
| 202Z | | | IB | 0-0 | 31-31-22 | D05700P | | | | FA | | | D01923 | DED | | | 050-099, 275-299 |
| 202Z | | | IB | 0-0 | 31-31-22 | D01923 | DED | | | | | | D05700P | | | FA | 150-199 |
| 302B | 18 | VH | F | 15-8 | 28-25-21 | D01564 | 3 | | | | | | D05700P | 14 | | | ALL |
| 302R | 18 | VH | F | 0-0 | 28-25-21 | D01564 | 5 | | | | | | D05700P | 4 | | | ALL |
| 302Y | 18 | VH | F | 0-0 | 28-25-21 | D01564 | 2 | | | | | | D05700P | 3 | | | ALL |
| 302Z | | | F | 0-0 | 28-25-21 | GD04072 | S.. | N | | | | | GD03942 | S.. | N | | ALL |
| 401B | 20 | U4 | D | 79-0 | 27-11-12 | D01634 | 4 | | | | | | D05700P | 10 | | | ALL |
| 401G | 20 | U4 | D | 0-0 | 27-11-12 | D01634 | 2 | | | | | | D05700P | 6 | | | ALL |
| 401R | 20 | U4 | D | 0-0 | 27-11-12 | D01634 | 1 | | | | | | D05700P | 5 | | | ALL |
| 401Y | 20 | U4 | D | 0-0 | 27-11-12 | D01634 | 5 | | | | | | D05700P | 11 | | | ALL |
| 401Z | | | D | 0-0 | 27-11-12 | GD03458 | S.. | N | | | | | GD03942 | S.. | N | | ALL |
| 402B | 20 | U4 | E | 47-8 | 28-21-13 | D01618 | 2 | | | | | | D05700P | 12 | | | ALL |
| 402G | 20 | U4 | E | 0-0 | 28-21-13 | D01618 | 5 | | | | | | D05700P | 13 | | | ALL |
| 402R | 20 | U4 | E | 0-0 | 28-21-13 | D01618 | 1 | | | | | | D05700P | 15 | | | ALL |
| 402Y | 20 | U4 | E | 0-0 | 28-21-13 | D01618 | 4 | | | | | | D05700P | 16 | | | ALL |
| 402Z | | | E | 0-0 | 28-21-13 | GD03454 | S.. | N | | | | | GD03942 | S.. | N | | ALL |
| FRA | | | | 0-0 | 31-31-22 | D05700P | | | | FA | | | D05700P | 8 | | | 050-099, 275-299 |
| FRA | | | | 6-0 | 31-31-22 | D05700P | 8 | | | | | | D05700P | | | FA | 150-199 |
| W0485 | 286T0485 | | | ILS-R,SHELF TO CONT PNL | | | | | | | | | | | | | |
| 001 | 20 | PA | | 29-0 | 34-31-21 | D04369J | 5 | | | | | | D00601 | 5 | | | ALL |
| 002 | 20 | PA | | 1-6 | 34-31-21 | GD04474 | S.. | 2 | | | | | D00601 | 7 | | | ALL |
| 003 | 22 | PA | | 29-0 | 34-31-21 | D04369J | 11 | | | | | | D00601 | 11 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0480

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0485 | 286T0485 | | | ILS-R,SHELF TO CONT PNL (continued) | | | | | | | | | | | |
| 004 | 22 | | PA | | 33-0 | 22-11-22 | D04369J | | | | TB0307F | A004 | 2 | | ALL |
| 005 | 22 | | PA | | 8-0 | 22-11-22 | TB0307F | | C004 | 2 | TB0207F | C004 | 2 | | ALL |
| 006 | 22 | | PA | | 28-0 | 22-11-22 | D04369J | | | 4 | TB0207F | A004 | 2 | | ALL |
| 007 | 22 | | PA | | 32-0 | 22-12-21 | D04369J | | | 1 | D04555P | | 1 | | ALL |
| 008 | 22 | | PA | | 32-0 | 22-12-21 | D04369J | | | 2 | D04555P | | 2 | | ALL |
| 009 | 20 | | PA | | 32-0 | 27-41-21 | D04369J | | | 13 | D04555P | | 7 | | ALL |
| 010 | 20 | | PA | | 32-0 | 27-41-21 | D04369J | | | 14 | D04555P | | 4 | | ALL |
| 011 | 24 | | PK | | 32-0 | 27-48-11 | D04369J | | | 15 | D02238 | | 8 | | 050-099, 150-154, 157-164, 167-199, 275-299 |
| 012 | 24 | | PK | | 32-0 | 27-48-11 | D04369J | | | 22 | D02238 | | 7 | | 050-099, 150-154, 157-164, 167-199, 275-299 |
| 013 | 24 | | PK | | 32-0 | 27-48-11 | D04369J | | | 23 | D02238 | | 6 | | 050-099, 150-154, 157-164, 167-199, 275-299 |
| 014 | 24 | | PK | | 32-0 | 31-51-42 | D04555P | | | 10 | D04369J | | 10 | | ALL |
| 015 | 20 | | PA | | 2-0 | 27-48-11 | D02238 | | | 3 | GD00617 | S.. | E | | ALL |
| 016 | 20 | | PA | | 2-0 | 27-48-11 | D02238 | | | 9 | GD00609 | A.. | 2 | | ALL |
| 017 | 20 | | PA | | 10-5 | 33-13-18 | D02238 | | | 1 | SP02282 | | 9 | | ALL |
| 018 | 20 | | PA | | 1-6 | 33-13-18 | D02238 | | | 2 | GD00609 | A.. | 2 | | ALL |
| 019 | 22 | | PA | | 32-0 | 22-12-21 | D04369J | | | 16 | D04555P | | 6 | | ALL |
| 020 | 24 | | PK | | 32-0 | SPARE | D04369J | | | 17 | D04555P | | 3 | | ALL |
| 021 | 24 | | PK | | 32-0 | 31-51-41 | D04369J | | | 21 | D04555P | | 5 | | ALL |
| 022 | 24 | | PK | | 32-0 | SPARE | D04369J | | | 24 | D04555P | | 9 | | ALL |
| 201B | 22 | | PB | IA | 29-0 | 34-31-21 | D04369J | | | 8 | D00601 | | 8 | | ALL |
| 201R | 22 | | PB | IA | 0-0 | 34-31-21 | D04369J | | | 9 | D00601 | | 9 | | ALL |
| 202B | 24 | | PW | IB | 29-0 | 34-31-21 | D04369J | | | 7 | D00601 | | 13 | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-31-21 | D04369J | | | 6 | D00601 | | 14 | | ALL |
| 202Z | | | | IB | 0-0 | 34-31-21 | D04369J | | | 12 | D00601 | | 12 | | ALL |
| 301B | 24 | | PM | MA | 32-0 | 27-48-11 | D04369J | | | 22 | D02238 | | 7 | | 155-156, 165-166 |
| 301R | 24 | | PM | MA | 0-0 | 27-48-11 | D04369J | | | 23 | D02238 | | 6 | | 155-156, 165-166 |
| 301Y | 24 | | PM | MA | 0-0 | 27-48-11 | D04369J | | | 15 | D02238 | | 8 | | 155-156, 165-166 |
| W0486 | 286T0486 | | | L WING TIP-R2-ANTI COLLISION LTS | | | | | | | | | | | |
| 201B | 12 | | UB | A | 2-10 | 33-43-11 | D04430P | | | 1 | D02078 | | 1 | | ALL |
| 201R | 12 | | UB | A | 0-0 | 33-43-11 | D04430P | | | 2 | D02078 | | 2 | | ALL |
| 202B | 12 | | UB | B | 2-10 | 33-43-11 | D04430P | | | 3 | D02078 | | 3 | | ALL |
| 202R | 12 | | UB | B | 0-0 | 33-43-11 | D04430P | | | 4 | D02078 | | 4 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0480
Page 7
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0487 | 286T0487 | | | VOR/DME L,SHELF TO CONT PNL | | | | | | | | | | | |
| 006 | 22 | PA | | 32-0 | 34-51-11 | D04373J | | 6 | | | D05415J | | 5 | | ALL |
| 017 | 24 | PK | | 32-0 | 34-55-11 | D05415J | | 1 | | | D04373J | | 7 | | ALL |
| 021 | 22 | PA | | 32-0 | SPARE | D04373J | | 3 | | | D05415J | | 21 | | ALL |
| 022 | 22 | PA | | 32-0 | SPARE | D04373J | | 4 | | | D05415J | | 22 | | ALL |
| 023 | 22 | PA | | 32-0 | SPARE | D04373J | | 5 | | | D05415J | | 23 | | ALL |
| 201B | 22 | PB | IA | 32-0 | 34-51-11 | D04373J | | 2 | | | D05415J | | 13 | | ALL |
| 201R | 22 | PB | IA | 0-0 | 34-51-11 | D04373J | | 1 | | | D05415J | | 12 | | ALL |
| 202B | 24 | PW | IB | 32-0 | 34-51-11 | D04373J | | 21 | | | D05415J | | 7 | | ALL |
| 202R | 24 | PW | IB | 0-0 | 34-51-11 | D04373J | | 8 | | | D05415J | | 6 | | ALL |
| 202Z | | | IB | 0-0 | 34-51-11 | D04373J | | 20 | | | D05415J | | 8 | | ALL |
| 203B | 24 | PW | IC | 32-0 | 34-51-11 | D04373J | | 22 | | | D05415J | | 15 | | ALL |
| 203R | 24 | PW | IC | 0-0 | 34-51-11 | D04373J | | 10 | | | D05415J | | 14 | | ALL |
| 203Z | | | IC | 0-0 | 34-51-11 | D04373J | | 23 | | | D05415J | | 16 | | ALL |
| 204B | 24 | PW | ID | 32-0 | 34-51-11 | D04373J | | 31 | | | D05415J | | 10 | | ALL |
| 204R | 24 | PW | ID | 0-0 | 34-51-11 | D04373J | | 18 | | | D05415J | | 9 | | ALL |
| 204Z | | | ID | 0-0 | 34-51-11 | D04373J | | 30 | | | D05415J | | 11 | | ALL |
| 205B | 24 | PW | IE | 32-0 | 34-55-11 | D04373J | | 29 | | | D05415J | | 3 | | ALL |
| 205R | 24 | PW | IE | 0-0 | 34-55-11 | D04373J | | 16 | | | D05415J | | 2 | | ALL |
| 205Z | | | IE | 0-0 | 34-55-11 | D04373J | | 28 | | | D05415J | | 4 | | ALL |
| 301 | 20 | UA | | 0-18 | 23-51-12 | D04373J | | | FA | | GD00557 | | S.. | E | ALL |
| 301B | 24 | PX | MA | 32-0 | 23-51-12 | D04373J | | 25 | | | D05415J | | 18 | | ALL |
| 301R | 24 | PX | MA | 0-0 | 23-51-12 | D04373J | | 24 | | | D05415J | | 17 | | ALL |
| 301Y | 24 | PX | MA | 0-0 | 23-51-12 | D04373J | | 12 | | | D05415J | | 19 | | ALL |
| 301Z | | | MA | 0-0 | 23-51-12 | D04373J | | | FA | | D05415J | | 20 | | ALL |
| W0488 | 286T0488 | | | L WING TIP-R2-ANTI COLLISION LTS | | | | | | | | | | | |
| 201B | 12 | UB | A | 4-7 | 33-43-11 | D04432P | | 1 | | | D02082 | | 1 | | ALL |
| 201R | 12 | UB | A | 0-0 | 33-43-11 | D04432P | | 2 | | | D02082 | | 2 | | ALL |
| 202B | 12 | UB | B | 4-7 | 33-43-11 | D04432P | | 3 | | | D02082 | | 3 | | ALL |
| 202R | 12 | UB | B | 0-0 | 33-43-11 | D04432P | | 4 | | | D02082 | | 4 | | ALL |
| W0489 | 286T0489 | | | VOR/DME R,SHELF TO CONT PNL | | | | | | | | | | | |
| 006 | 22 | PA | | 28-0 | 34-51-21 | D04377J | | 6 | | | D05417J | | 5 | | ALL |
| 019 | 24 | PK | | 28-0 | 34-55-21 | D05417J | | 1 | | | D04377J | | 7 | | ALL |
| 021 | 22 | PA | | 28-0 | SPARE | D04377J | | 3 | | | D05417J | | 21 | | ALL |
| 022 | 22 | PA | | 28-0 | SPARE | D04377J | | 4 | | | D05417J | | 22 | | ALL |
| 023 | 22 | PA | | 28-0 | SPARE | D04377J | | 5 | | | D05417J | | 23 | | ALL |
| 201B | 22 | PB | IA | 28-0 | 34-51-21 | D04377J | | 2 | | | D05417J | | 13 | | ALL |
| 201R | 22 | PB | IA | 0-0 | 34-51-21 | D04377J | | 1 | | | D05417J | | 12 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0480

Page 8

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0489 | 286T0489 | | | VOR/DME R,SHELF TO CONT PNL (continued) | | | | | | | | | | | |
| 202B | 24 | PW | IB | 28-0 | 34-51-21 | D04377J | | 21 | | | D05417J | | 7 | | ALL |
| 202R | 24 | PW | IB | 0-0 | 34-51-21 | D04377J | | 8 | | | D05417J | | 6 | | ALL |
| 202Z | | | IB | 0-0 | 34-51-21 | D04377J | | 20 | | | D05417J | | 8 | | ALL |
| 203B | 24 | PW | IC | 28-0 | 34-51-21 | D04377J | | 22 | | | D05417J | | 15 | | ALL |
| 203R | 24 | PW | IC | 0-0 | 34-51-21 | D04377J | | 10 | | | D05417J | | 14 | | ALL |
| 203Z | | | IC | 0-0 | 34-51-21 | D04377J | | 23 | | | D05417J | | 16 | | ALL |
| 204B | 24 | PW | ID | 28-0 | 34-51-21 | D04377J | | 31 | | | D05417J | | 10 | | ALL |
| 204R | 24 | PW | ID | 0-0 | 34-51-21 | D04377J | | 18 | | | D05417J | | 9 | | ALL |
| 204Z | | | ID | 0-0 | 34-51-21 | D04377J | | 30 | | | D05417J | | 11 | | ALL |
| 205B | 24 | PW | IE | 28-0 | 34-55-21 | D04377J | | 29 | | | D05417J | | 3 | | ALL |
| 205R | 24 | PW | IE | 0-0 | 34-55-21 | D04377J | | 16 | | | D05417J | | 2 | | ALL |
| 205Z | | | IE | 0-0 | 34-55-21 | D04377J | | 28 | | | D05417J | | 4 | | ALL |
| 301 | 20 | UA | | 3-0 | 23-51-12 | D04377J | | | | FA | GD00555 | S.. | E | | ALL |
| 301B | 24 | PX | MA | 28-0 | 23-51-12 | D04377J | | 25 | | | D05417J | | 18 | | ALL |
| 301R | 24 | PX | MA | 0-0 | 23-51-12 | D04377J | | 24 | | | D05417J | | 17 | | ALL |
| 301Y | 24 | PX | MA | 0-0 | 23-51-12 | D04377J | | 12 | | | D05417J | | 19 | | ALL |
| 301Z | | | MA | 0-0 | 23-51-12 | D04377J | | | | FA | D05417J | | 20 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0480
Page 9 End
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0490 | 286T0490 | | | R WING TIP-R2-ANTI COLLISION LTS | | | | | | | | | | | | |
| 201B | 12 | UB | A | 2-10 | 33-43-11 | D04426P | | 1 | | | D02080 | | 1 | | ALL | |
| 201R | 12 | UB | A | 0-0 | 33-43-11 | D04426P | | 2 | | | D02080 | | 2 | | ALL | |
| 202B | 12 | UB | B | 2-10 | 33-43-11 | D04426P | | 3 | | | D02080 | | 3 | | ALL | |
| 202R | 12 | UB | B | 0-0 | 33-43-11 | D04426P | | 4 | | | D02080 | | 4 | | ALL | |
| W0491 | 286T0491 | | | PITCH SERVO ACTR,RO SERVO ACTR & STAB POS XMTR L | | | | | | | | | | | | |
| 001 | 22 | PA | | 125-7 | 22-11-12 | D04379J | | 1 | | | D04475P | | 1 | | 050 | |
| 001 | 22 | PA | | 125-9 | 22-11-12 | D04379J | | 1 | | | D04475P | | 1 | | 051-099 | |
| 001 | 22 | PA | | 146-11 | 22-11-12 | D04379J | | 1 | | | D04475P | | 1 | | 150-199, 275-299 | |
| 002 | 22 | PA | | 125-7 | 22-11-12 | D04379J | | 52 | | | D04475P | | 14 | | 050 | |
| 002 | 22 | PA | | 125-9 | 22-11-12 | D04379J | | 52 | | | D04475P | | 14 | | 051-099 | |
| 002 | 22 | PA | | 146-11 | 22-11-12 | D04379J | | 52 | | | D04475P | | 14 | | 150-199, 275-299 | |
| 003 | 22 | PA | | 125-5 | 22-11-12 | D04379J | | 37 | | | D04519P | | 3 | | 050 | |
| 003 | 22 | PA | | 125-11 | 22-11-12 | D04379J | | 37 | | | D04519P | | 3 | | 051-099 | |
| 003 | 22 | PA | | 147-0 | 22-11-12 | D04379J | | 37 | | | D04519P | | 3 | | 150-199, 275-299 | |
| 004 | 22 | PA | | 125-5 | 22-11-12 | D04379J | | 49 | | | D04519P | | 9 | | 050 | |
| 004 | 22 | PA | | 125-11 | 22-11-12 | D04379J | | 49 | | | D04519P | | 9 | | 051-099 | |
| 004 | 22 | PA | | 147-0 | 22-11-12 | D04379J | | 49 | | | D04519P | | 9 | | 150-199, 275-299 | |
| 005 | 20 | PA | | 125-3 | 27-41-11 | D04379J | | 26 | | | D04531P | | 6 | | 050 | |
| 005 | 20 | PA | | 125-7 | 27-41-11 | D04379J | | 26 | | | D04531P | | 6 | | 051-099 | |
| 005 | 20 | PA | | 146-11 | 27-41-11 | D04379J | | 26 | | | D04531P | | 6 | | 150-199, 275-299 | |
| 006 | 20 | PA | | 125-3 | 27-41-11 | D04379J | | 27 | | | D04531P | | 7 | | 050 | |
| 006 | 20 | PA | | 125-7 | 27-41-11 | D04379J | | 27 | | | D04531P | | 7 | | 051-099 | |
| 006 | 20 | PA | | 146-11 | 27-41-11 | D04379J | | 27 | | | D04531P | | 7 | | 150-199, 275-299 | |
| 007Y | 22 | PJ | | 125-3 | 27-41-11 | D04379J | | 28 | | | D04531P | | 8 | | 050 | |
| 007Y | 22 | PJ | | 125-7 | 27-41-11 | D04379J | | 28 | | | D04531P | | 8 | | 051-099 | |
| 007Y | 22 | PJ | | 146-11 | 27-41-11 | D04379J | | 28 | | | D04531P | | 8 | | 150-199, 275-299 | |
| 008Y | 22 | PJ | | 125-3 | 27-41-11 | D04379J | | 29 | | | D04531P | | 9 | | 050 | |
| 008Y | 22 | PJ | | 125-7 | 27-41-11 | D04379J | | 29 | | | D04531P | | 9 | | 051-099 | |
| 009 | 20 | PA | | 125-5 | SPARE | D04379J | | 39 | | | D04519P | | 4 | | 050 | |
| 009 | 20 | PA | | 125-11 | SPARE | D04379J | | 39 | | | D04519P | | 4 | | 051-099 | |
| 009 | 20 | PA | | 147-0 | SPARE | D04379J | | 39 | | | D04519P | | 4 | | 150-199, 275-299 | |
| 010Y | 22 | PJ | | 125-3 | 27-41-11 | D04379J | | 40 | | | D04531P | | 10 | | 050 | |
| 010Y | 22 | PJ | | 125-7 | 27-41-11 | D04379J | | 40 | | | D04531P | | 10 | | 051-099 | |
| 010Y | 22 | PJ | | 146-11 | 27-41-11 | D04379J | | 40 | | | D04531P | | 10 | | 150-199, 275-299 | |
| 011 | 24 | PK | | 125-3 | 27-48-11 | D04379J | | 41 | | | D04531P | | 1 | | 050 | |
| 011 | 24 | PK | | 125-7 | 27-48-11 | D04379J | | 41 | | | D04531P | | 1 | | 051-099 | |
| 011 | 24 | PK | | 146-11 | 27-48-11 | D04379J | | 41 | | | D04531P | | 1 | | 150-154, 157-164, 167-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0490

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0491 | 286T0491 | | | PITCH SERVO ACTR,RO SERVO ACTR & STAB POS XMTR L (continued) | | | | | | | | | | | |
| 012 | 24 | | PK | 138-3 | 27-48-11 | D04385J | 42 | | | D04531P | 2 | | | 050 | |
| 012 | 24 | | PK | 129-3 | 27-48-11 | D04385J | 42 | | | D04531P | 2 | | | 051-099 | |
| 012 | 24 | | PK | 146-11 | 27-48-11 | D04379J | 42 | | | D04531P | 2 | | | 150-154, 275-276 | |
| 012 | 24 | | PK | 160-5 | 27-48-11 | D04385J | 42 | | | D04531P | 2 | | | 162-164 | |
| 013 | 24 | | PK | 138-3 | 27-48-11 | D04385J | 43 | | | D04531P | 3 | | | 050 | |
| 013 | 24 | | PK | 129-3 | 27-48-11 | D04385J | 43 | | | D04531P | 3 | | | 051-099 | |
| 013 | 24 | | PK | 146-11 | 27-48-11 | D04379J | 43 | | | D04531P | 3 | | | 150-154, 275-276 | |
| 013 | 24 | | PK | 160-5 | 27-48-11 | D04385J | 43 | | | D04531P | 3 | | | 162-164 | |
| 014 | 20 | | PA | 125-5 | 27-21-11 | D04379J | 38 | | | D04519P | 5 | | | 050 | |
| 014 | 20 | | PA | 125-11 | 27-21-11 | D04379J | 38 | | | D04519P | 5 | | | 051-099 | |
| 014 | 20 | | PA | 147-0 | 27-21-11 | D04379J | 38 | | | D04519P | 5 | | | 150-199, 275-299 | |
| 016 | 20 | | PA | 125-5 | SPARE | D04379J | 36 | | | D04519P | 6 | | | 050 | |
| 016 | 20 | | PA | 125-11 | SPARE | D04379J | 36 | | | D04519P | 6 | | | 051-099 | |
| 016 | 20 | | PA | 147-0 | SPARE | D04379J | 36 | | | D04519P | 6 | | | 150-199, 275-299 | |
| 017Y | 22 | | PJ | 125-7 | 27-41-11 | D04379J | 33 | | | D04475P | 3 | | | 050 | |
| 017Y | 22 | | PJ | 125-9 | 27-41-11 | D04379J | 33 | | | D04475P | 3 | | | 051-099 | |
| 017Y | 22 | | PJ | 146-11 | 27-41-11 | D04379J | 33 | | | D04475P | 3 | | | 150-199, 275-299 | |
| 018 | 16 | | PA | 125-7 | 27-32-31 | D04379J | 53 | FM | | D04475P | 20 | FM | | 050 | |
| 018 | 16 | | PA | 125-9 | 27-32-31 | D04379J | 53 | FM | | D04475P | 20 | FM | | 051-099 | |
| 018 | 16 | | PA | 146-11 | 27-32-31 | D04379J | 53 | FM | | D04475P | 20 | FM | | 150-199, 275-299 | |
| 019 | 16 | | PA | 125-7 | 27-32-31 | D04379J | 55 | FM | | D04475P | 24 | FM | | 050 | |
| 019 | 16 | | PA | 125-9 | 27-32-31 | D04379J | 55 | FM | | D04475P | 24 | FM | | 051-099 | |
| 019 | 16 | | PA | 146-11 | 27-32-31 | D04379J | 55 | FM | | D04475P | 24 | FM | | 150-199, 275-299 | |
| 020 | 20 | | PA | 125-7 | SPARE | D04379J | 31 | | | D04475P | 16 | | | 050 | |
| 020 | 20 | | PA | 125-9 | SPARE | D04379J | 31 | | | D04475P | 16 | | | 051-099 | |
| 020 | 20 | | PA | 146-11 | SPARE | D04379J | 31 | | | D04475P | 16 | | | 150-199, 275-299 | |
| 021Y | 22 | | PJ | 146-11 | SPARE | D04379J | 29 | | | D04531P | 9 | | | 150-199, 275-299 | |
| 201B | 22 | | PB IA | 125-7 | 22-11-11 | D04379J | 6 | | | D04475P | 5 | | | 050 | |
| 201B | 22 | | PB IA | 125-9 | 22-11-11 | D04379J | 6 | | | D04475P | 5 | | | 051-099 | |
| 201B | 22 | | PB IA | 146-11 | 22-11-11 | D04379J | 6 | | | D04475P | 5 | | | 150-199, 275-299 | |
| 201R | 22 | | PB IA | 0-0 | 22-11-11 | D04379J | 5 | | | D04475P | 4 | | | ALL | |
| 202B | 22 | | PB IB | 125-5 | 22-11-11 | D04379J | 8 | | | D04519P | 8 | | | 050 | |
| 202B | 22 | | PB IB | 125-11 | 22-11-11 | D04379J | 8 | | | D04519P | 8 | | | 051-099 | |
| 202B | 22 | | PB IB | 147-0 | 22-11-11 | D04379J | 8 | | | D04519P | 8 | | | 150-199, 275-299 | |
| 202R | 22 | | PB IB | 0-0 | 22-11-11 | D04379J | 7 | | | D04519P | 7 | | | ALL | |
| 203B | 24 | | PL IC | 125-3 | 27-58-21 | D04379J | 44 | | | D04531P | 11 | | | 050 | |
| 203B | 24 | | PL IC | 125-7 | 27-58-21 | D04379J | 44 | | | D04531P | 11 | | | 051-099 | |
| 203B | 24 | | PL IC | 146-11 | 27-58-21 | D04379J | 44 | | | D04531P | 11 | | | 150-199, 275-299 | |
| 203R | 24 | | PL IC | 0-0 | 27-58-21 | D04379J | 45 | | | D04531P | 12 | | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W0490
Page 2
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|--------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0491 | 286T0491 | | | PITCH SERVO ACTR,RO SERVO ACTR & STAB POS XMTR L (continued) | | | | | | | | | | | |
| 204B | 22 | PB | ID | | 125-7 | 22-12-11 | D04379J | | 10 | | D04475P | | 10 | | 050 |
| 204B | 22 | PB | ID | | 125-9 | 22-12-11 | D04379J | | 10 | | D04475P | | 10 | | 051-099 |
| 204B | 22 | PB | ID | | 146-11 | 22-12-11 | D04379J | | 10 | | D04475P | | 10 | | 150-199, 275-299 |
| 204R | 22 | PB | ID | | 0-0 | 22-12-11 | D04379J | | 9 | | D04475P | | 9 | | ALL |
| 205B | 22 | PB | IE | | 125-5 | 22-13-11 | D04379J | | 18 | | D04519P | | 2 | | 050 |
| 205B | 22 | PB | IE | | 125-11 | 22-13-11 | D04379J | | 18 | | D04519P | | 2 | | 051-099 |
| 205B | 22 | PB | IE | | 147-0 | 22-13-11 | D04379J | | 18 | | D04519P | | 2 | | 150-199, 275-299 |
| 205R | 22 | PB | IE | | 0-0 | 22-13-11 | D04379J | | 17 | | D04519P | | 1 | | ALL |
| 206B | 22 | PB | IF | | 125-7 | SPARE | D04379J | | 35 | | D04475P | | 15 | | 050 |
| 206B | 22 | PB | IF | | 125-9 | SPARE | D04379J | | 35 | | D04475P | | 15 | | 051-099 |
| 206B | 22 | PB | IF | | 146-11 | SPARE | D04379J | | 35 | | D04475P | | 15 | | 150-199, 275-299 |
| 206R | 22 | PB | IF | | 0-0 | SPARE | D04379J | | 34 | | D04475P | | 2 | | ALL |
| 301B | 24 | PM | MA | | 125-3 | 27-58-21 | D04379J | | 46 | | D04531P | | 13 | | 050 |
| 301B | 24 | PM | MA | | 125-7 | 27-58-21 | D04379J | | 46 | | D04531P | | 13 | | 051-099 |
| 301B | 24 | PM | MA | | 146-11 | 27-58-21 | D04379J | | 46 | | D04531P | | 13 | | 150-199, 275-299 |
| 301R | 24 | PM | MA | | 0-0 | 27-58-21 | D04379J | | 47 | | D04531P | | 14 | | ALL |
| 301Y | 24 | PM | MA | | 0-0 | 27-58-21 | D04379J | | 48 | | D04531P | | 15 | | ALL |
| 302B | 22 | PC | MB | | 125-7 | 22-12-11 | D04379J | | 12 | | D04475P | | 12 | | 050 |
| 302B | 22 | PC | MB | | 125-9 | 22-12-11 | D04379J | | 12 | | D04475P | | 12 | | 051-099 |
| 302B | 22 | PC | MB | | 146-11 | 22-12-11 | D04379J | | 12 | | D04475P | | 12 | | 150-199, 275-299 |
| 302R | 22 | PC | MB | | 0-0 | 22-12-11 | D04379J | | 11 | | D04475P | | 11 | | ALL |
| 302Y | 22 | PC | MB | | 0-0 | 22-12-11 | D04379J | | 13 | | D04475P | | 13 | | ALL |
| 303B | 22 | PC | MC | | 125-7 | 22-12-11 | D04379J | | 15 | | D04475P | | 7 | | 050 |
| 303B | 22 | PC | MC | | 125-9 | 22-12-11 | D04379J | | 15 | | D04475P | | 7 | | 051-099 |
| 303B | 22 | PC | MC | | 146-11 | 22-12-11 | D04379J | | 15 | | D04475P | | 7 | | 150-199, 275-299 |
| 303R | 22 | PC | MC | | 0-0 | 22-12-11 | D04379J | | 14 | | D04475P | | 6 | | ALL |
| 303Y | 22 | PC | MC | | 0-0 | 22-12-11 | D04379J | | 16 | | D04475P | | 8 | | ALL |
| 304B | 22 | PC | MD | | 125-5 | 22-13-11 | D04379J | | 20 | | D04519P | | 11 | | 050 |
| 304B | 22 | PC | MD | | 125-11 | 22-13-11 | D04379J | | 20 | | D04519P | | 11 | | 051-099 |
| 304B | 22 | PC | MD | | 147-0 | 22-13-11 | D04379J | | 20 | | D04519P | | 11 | | 150-199, 275-299 |
| 304R | 22 | PC | MD | | 0-0 | 22-13-11 | D04379J | | 19 | | D04519P | | 10 | | ALL |
| 304Y | 22 | PC | MD | | 0-0 | 22-13-11 | D04379J | | 21 | | D04519P | | 12 | | ALL |
| 305B | 22 | PC | ME | | 125-5 | 22-13-11 | D04379J | | 23 | | D04519P | | 14 | | 050 |
| 305B | 22 | PC | ME | | 125-11 | 22-13-11 | D04379J | | 23 | | D04519P | | 14 | | 051-099 |
| 305B | 22 | PC | ME | | 147-0 | 22-13-11 | D04379J | | 23 | | D04519P | | 14 | | 150-199, 275-299 |
| 305R | 22 | PC | ME | | 0-0 | 22-13-11 | D04379J | | 22 | | D04519P | | 13 | | ALL |
| 305Y | 22 | PC | ME | | 0-0 | 22-13-11 | D04379J | | 24 | | D04519P | | 15 | | ALL |
| 307B | 24 | PM | MG | | 151-10 | 27-48-11 | D04385J | | 42 | | D04533P | | 2 | | 155-156, 166 |

WIRE LIST

D280T132

91-21-11

Section W0490

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|--------|----------|---------|------|------|--------|---------|------|------|--------|-------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0491 | 286T0491 | | | PITCH SERVO ACTR,RO SERVO ACTR & STAB POS XMTR L (continued) | | | | | | | | | | | |
| 307B | 24 | | PM | MG | 146-11 | 27-48-11 | D04379J | | 42 | | D04531P | | 2 | | 157, 165, 167-199, 277-299 |
| 307R | 24 | | PM | MG | 0-0 | 27-48-11 | D04385J | | 43 | | D04533P | | 3 | | 155-156, 166 |
| 307R | 24 | | PM | MG | 0-0 | 27-48-11 | D04379J | | 43 | | D04531P | | 3 | | 157, 165, 167-199, 277-299 |
| 307Y | 24 | | PM | MG | 0-0 | 27-48-11 | D04385J | | 41 | | D04533P | | 1 | | 155-156, 166 |
| 307Y | 24 | | PM | MG | 0-0 | 27-48-11 | D04379J | | 4 | | D04531P | | 4 | | 157, 167-199, 277-299 |
| 307Y | 24 | | PM | MG | 0-0 | 27-48-11 | D04379J | | 41 | | D04531P | | 1 | | 165 |
| 70N | 20 | | PA | | 125-7 | 29-11-14 | D04379J | | 51 | | D04475P | | 22 | | 050 |
| 70N | 20 | | PA | | 125-9 | 29-11-14 | D04379J | | 51 | | D04475P | | 22 | | 051-099 |
| 70N | 20 | | PA | | 146-11 | 29-11-14 | D04379J | | 51 | | D04475P | | 22 | | 150-199, 275-299 |
| 70P | 20 | | PA | | 125-7 | 29-11-14 | D04379J | | 54 | | D04475P | | 23 | | 050 |
| 70P | 20 | | PA | | 125-9 | 29-11-14 | D04379J | | 54 | | D04475P | | 23 | | 051-099 |
| 70P | 20 | | PA | | 146-11 | 29-11-14 | D04379J | | 54 | | D04475P | | 23 | | 150-199, 275-299 |
| W0492 | 286T0492 | | | R WING TIP-R2-ANTI COLLISION LTS | | | | | | | | | | | |
| 201B | 12 | | UB | A | 4-7 | 33-43-11 | D04428P | | 1 | | D02084 | | 1 | | ALL |
| 201R | 12 | | UB | A | 0-0 | 33-43-11 | D04428P | | 2 | | D02084 | | 2 | | ALL |
| 202B | 12 | | UB | B | 4-7 | 33-43-11 | D04428P | | 3 | | D02084 | | 3 | | ALL |
| 202R | 12 | | UB | B | 0-0 | 33-43-11 | D04428P | | 4 | | D02084 | | 4 | | ALL |
| W0495 | 286T0495 | | | CCA & FLAP POS XMTR,L | | | | | | | | | | | |
| 001 | 20 | | PA | | 74-0 | 22-11-12 | D04383J | | 11 | | D04807J | | 11 | | 050-099 |
| 001 | 20 | | PA | | 83-0 | 22-11-12 | D04383J | | 11 | | D04807J | | 11 | | 150-199, 275-299 |
| 002 | 20 | | PA | | 74-0 | 22-11-12 | D04383J | | 14 | | D04807J | | 14 | | 050-099 |
| 002 | 20 | | PA | | 83-0 | 22-11-12 | D04383J | | 14 | | D04807J | | 14 | | 150-199, 275-299 |
| 201B | 20 | | PB | IA | 74-0 | 22-11-11 | D04383J | | 2 | | D04807J | | 2 | | 050-099 |
| 201B | 20 | | PB | IA | 83-0 | 22-11-11 | D04383J | | 2 | | D04807J | | 2 | | 150-199, 275-299 |
| 201R | 20 | | PB | IA | 0-0 | 22-11-11 | D04383J | | 1 | | D04807J | | 1 | | ALL |
| 202B | 20 | | PB | IB | 74-0 | 22-13-11 | D04383J | | 4 | | D04807J | | 4 | | 050-099 |
| 202B | 20 | | PB | IB | 83-0 | 22-13-11 | D04383J | | 4 | | D04807J | | 4 | | 150-199, 275-299 |
| 202R | 20 | | PB | IB | 0-0 | 22-13-11 | D04383J | | 3 | | D04807J | | 3 | | ALL |
| 301B | 20 | | PC | MA | 74-0 | 22-13-11 | D04383J | | 6 | | D04807J | | 6 | | 050-099 |
| 301B | 20 | | PC | MA | 83-0 | 22-13-11 | D04383J | | 6 | | D04807J | | 6 | | 150-199, 275-299 |
| 301R | 20 | | PC | MA | 0-0 | 22-13-11 | D04383J | | 5 | | D04807J | | 5 | | ALL |
| 301Y | 20 | | PC | MA | 0-0 | 22-13-11 | D04383J | | 7 | | D04807J | | 7 | | ALL |
| 302B | 20 | | PC | MB | 74-0 | 22-13-11 | D04383J | | 9 | | D04807J | | 9 | | 050-099 |
| 302B | 20 | | PC | MB | 83-0 | 22-13-11 | D04383J | | 9 | | D04807J | | 9 | | 150-199, 275-299 |
| 302R | 20 | | PC | MB | 0-0 | 22-13-11 | D04383J | | 8 | | D04807J | | 8 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0490

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0495 | 286T0495 | | | CCA & FLAP POS XMTR,L (continued) | | | | | | | | | | | |
| 302Y | 20 | PC | MB | | 0-0 | 22-13-11 | D04383J | | 10 | | D04807J | | 10 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0490
Page 5 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0500 | 286T0500 | | | V FIN-L2-FLT CONT | | | | | | | | | | | | |
| 001 | 20 | | UA | | 31-3 | 27-28-11 | D05436J | | | | D01892 | | | | 2 | ALL |
| 002 | 20 | | UA | | 31-3 | 27-28-11 | D05436J | | | | D01892 | | | | 5 | ALL |
| 003 | 20 | | UA | | 31-3 | 27-28-11 | D05436J | | | | D01892 | | | | 4 | ALL |
| 004 | 18 | | UA | | 2-10 | 27-28-11 | GD00796 | A.. | N | | D01892 | | 1 | DK | | ALL |
| 011 | 20 | | UA | | 27-10 | 27-21-11 | D05436J | | | | D01894 | | | | 2 | ALL |
| 012 | 18 | | VF | B | 26-8 | 27-21-11 | SP00752 | | 9 | | D01894 | | | | 3 | ALL |
| 012Z | | | | B | 0-0 | 27-21-11 | SP00752 | DED | | | D01894 | | DED | | | ALL |
| 013 | 18 | | UA | | 1-3 | 27-21-11 | GD00804 | S.. | N | | D01894 | | | | 12 | ALL |
| 014 | 18 | | UA | | 1-4 | 27-21-11 | GD00802 | D.. | N | | D01894 | | | | 1 | ALL |
| 015 | 20 | | UA | | 27-10 | 27-28-13 | D05436J | | | | D01894 | | | | 6 | ALL |
| 016 | 18 | | UA | | 1-7 | 27-28-13 | GD00800 | A.. | N | | D01894 | | | | 7 | ALL |
| 017 | 20 | | UA | | 31-3 | 27-28-11 | D05436J | | | | D01892 | | | | 3 | 155-157, 166-199, 277-299 |
| 201B | 20 | | UB | A | 27-10 | 27-28-13 | D05436J | | | | D01894 | | | | 4 | ALL |
| 201R | 20 | | UB | A | 0-0 | 27-28-13 | D05436J | | | | D01894 | | | | 5 | ALL |
| W0501 | 286T0501 | | | PITCH SERVO ACTR,RO SERVO ACTR & STAB POS XMTR C | | | | | | | | | | | | |
| 001 | 22 | | PA | | 130-2 | 22-11-32 | D04381J | | | | D04481P | | | | 1 | 050-099 |
| 001 | 22 | | PA | | 151-5 | 22-11-32 | D04381J | | | | D04481P | | | | 1 | 150-199, 275-299 |
| 002 | 22 | | PA | | 130-2 | 22-11-32 | D04381J | | | | D04481P | | | | 14 | 050-099 |
| 002 | 22 | | PA | | 151-5 | 22-11-32 | D04381J | | | | D04481P | | | | 14 | 150-199, 275-299 |
| 003 | 22 | | PA | | 130-6 | 22-11-32 | D04381J | | | | D04523P | | | | 3 | 050-099 |
| 003 | 22 | | PA | | 151-7 | 22-11-32 | D04381J | | | | D04523P | | | | 3 | 150-199, 275-299 |
| 004 | 22 | | PA | | 130-6 | 22-11-32 | D04381J | | | | D04523P | | | | 9 | 050-099 |
| 004 | 22 | | PA | | 151-7 | 22-11-32 | D04381J | | | | D04523P | | | | 9 | 150-199, 275-299 |
| 009 | 22 | | PA | | 130-6 | SPARE | D04381J | | | | D04523P | | | | 4 | 050-099 |
| 009 | 22 | | PA | | 151-7 | SPARE | D04381J | | | | D04523P | | | | 4 | 150-199, 275-299 |
| 013 | 22 | | PA | | 130-2 | SPARE | D04381J | | | | D04481P | | | | 3 | 050-099 |
| 013 | 22 | | PA | | 151-5 | SPARE | D04381J | | | | D04481P | | | | 3 | 150-199, 275-299 |
| 201B | 22 | | PB | IA | 130-2 | 22-11-31 | D04381J | | | | D04481P | | | | 5 | 050-099 |
| 201B | 22 | | PB | IA | 151-5 | 22-11-31 | D04381J | | | | D04481P | | | | 5 | 150-199, 275-299 |
| 201R | 22 | | PB | IA | 0-0 | 22-11-31 | D04381J | | | | D04481P | | | | 4 | ALL |
| 202B | 22 | | PB | IB | 130-6 | 22-11-31 | D04381J | | | | D04523P | | | | 8 | 050-099 |
| 202B | 22 | | PB | IB | 151-7 | 22-11-31 | D04381J | | | | D04523P | | | | 8 | 150-199, 275-299 |
| 202R | 22 | | PB | IB | 0-0 | 22-11-31 | D04381J | | | | D04523P | | | | 7 | ALL |
| 204B | 22 | | PB | ID | 130-2 | 22-12-31 | D04381J | | | | D04481P | | | | 10 | 050-099 |
| 204B | 22 | | PB | ID | 151-5 | 22-12-31 | D04381J | | | | D04481P | | | | 10 | 150-199, 275-299 |
| 204R | 22 | | PB | ID | 0-0 | 22-12-31 | D04381J | | | | D04481P | | | | 9 | ALL |
| 205B | 22 | | PB | IE | 130-6 | 22-13-31 | D04381J | | | | D04523P | | | | 2 | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | Effectivity |
|--------------|-----------------|---|-------|-------|-------------|---------|-------|------|------|--------|---------|------|------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | |
| W0501 | 286T0501 | PITCH SERVO ACTR,RO SERVO ACTR & STAB POS XMTR C (continued) | | | | | | | | | | | | |
| 205B | 22 | PB | IE | 151-7 | 22-13-31 | D04381J | | 18 | | | D04523P | 2 | | 150-199, 275-299 |
| 205R | 22 | PB | IE | 0-0 | 22-13-31 | D04381J | | 17 | | | D04523P | 1 | | ALL |
| 206B | 22 | PB | IF | 130-6 | SPARE | D04381J | | 26 | | | D04523P | 6 | | 050-099 |
| 206B | 22 | PB | IF | 151-7 | SPARE | D04381J | | 26 | | | D04523P | 6 | | 150-199, 275-299 |
| 206R | 22 | PB | IF | 0-0 | SPARE | D04381J | | 25 | | | D04523P | 5 | | ALL |
| 207B | 22 | PB | IG | 130-2 | SPARE | D04381J | | 35 | | | D04481P | 15 | | 050-099 |
| 207B | 22 | PB | IG | 151-5 | SPARE | D04381J | | 35 | | | D04481P | 15 | | 150-199, 275-299 |
| 207R | 22 | PB | IG | 0-0 | SPARE | D04381J | | 34 | | | D04481P | 2 | | ALL |
| 302B | 22 | PC | MB | 130-2 | 22-12-31 | D04381J | | 12 | | | D04481P | 12 | | 050-099 |
| 302B | 22 | PC | MB | 151-5 | 22-12-31 | D04381J | | 12 | | | D04481P | 12 | | 150-199, 275-299 |
| 302R | 22 | PC | MB | 0-0 | 22-12-31 | D04381J | | 11 | | | D04481P | 11 | | ALL |
| 302Y | 22 | PC | MB | 0-0 | 22-12-31 | D04381J | | 13 | | | D04481P | 13 | | ALL |
| 303B | 22 | PC | MC | 130-2 | 22-12-31 | D04381J | | 15 | | | D04481P | 7 | | 050-099 |
| 303B | 22 | PC | MC | 151-5 | 22-12-31 | D04381J | | 15 | | | D04481P | 7 | | 150-199, 275-299 |
| 303R | 22 | PC | MC | 0-0 | 22-12-31 | D04381J | | 14 | | | D04481P | 6 | | ALL |
| 303Y | 22 | PC | MC | 0-0 | 22-12-31 | D04381J | | 16 | | | D04481P | 8 | | ALL |
| 304B | 22 | PC | MD | 130-6 | 22-13-31 | D04381J | | 20 | | | D04523P | 11 | | 050-099 |
| 304B | 22 | PC | MD | 151-7 | 22-13-31 | D04381J | | 20 | | | D04523P | 11 | | 150-199, 275-299 |
| 304R | 22 | PC | MD | 0-0 | 22-13-31 | D04381J | | 19 | | | D04523P | 10 | | ALL |
| 304Y | 22 | PC | MD | 0-0 | 22-13-31 | D04381J | | 21 | | | D04523P | 12 | | ALL |
| 305B | 22 | PC | ME | 130-6 | 22-13-31 | D04381J | | 23 | | | D04523P | 14 | | 050-099 |
| 305B | 22 | PC | ME | 151-7 | 22-13-31 | D04381J | | 23 | | | D04523P | 14 | | 150-199, 275-299 |
| 305R | 22 | PC | ME | 0-0 | 22-13-31 | D04381J | | 22 | | | D04523P | 13 | | ALL |
| 305Y | 22 | PC | ME | 0-0 | 22-13-31 | D04381J | | 24 | | | D04523P | 15 | | ALL |
| W0502 | 286T0502 | L HORIZ STAB-L2B-FLT CONT | | | | | | | | | | | | |
| 001 | 20 | UA | | 29-10 | 27-38-11 | D05438J | | 1 | | | SP01742 | 9 | | ALL |
| 002 | 20 | UA | | 29-10 | 27-38-11 | D05438J | | 2 | | | SP02654 | 9 | | ALL |
| 003 | 20 | UA | | 29-10 | 27-38-11 | D05438J | | 3 | | | SP02658 | 9 | | ALL |
| 006 | 20 | UA | | 22-9 | 27-23-11 | D05438J | | 5 | | | D01888 | 10 | | ALL |
| 007 | 20 | UA | | 22-9 | 27-23-11 | D05438J | | 4 | | | D01888 | 2 | | ALL |
| 008 | 20 | UA | | 22-9 | 27-23-11 | D05438J | | 7 | | | D01888 | 3 | | ALL |
| 009 | 18 | UA | | 2-11 | 27-23-11 | GD00808 | D.. | N | | | D01888 | 1 | | ALL |
| 010 | 18 | UA | | 2-11 | 27-23-11 | GD00808 | D.. | N | | | D01888 | 9 | | ALL |
| 011 | 20 | UA | | 29-10 | 27-38-11 | D05438J | | 6 | | | SP01728 | 9 | | ALL |
| 012 | 20 | UA | | 29-10 | 27-38-11 | D05438J | | 8 | | | SP02646 | 9 | | ALL |
| 013 | 20 | UA | | 29-10 | 27-38-11 | D05438J | | 9 | | | SP02650 | 9 | | ALL |
| 016 | 18 | UA | | 1-11 | 27-31-11 | SM00001 | | | 9 | | D00432 | 2 | DK | ALL |
| 017 | 18 | UA | | 1-11 | 27-31-11 | SM00001 | | | 9 | | D00432 | 4 | DK | ALL |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0502 | 286T0502 | | | L HORIZ STAB-L2B-FLT CONT (continued) | | | | | | | | | | | |
| 018 | 18 | | UA | | 4-6 | 27-31-11 | GD03550 | D.. | N | | D00432 | 1 | DK | | ALL |
| 019 | 18 | | UA | | 4-6 | 27-31-11 | GD03550 | D.. | N | | D00432 | 3 | DK | | ALL |
| 020 | 18 | | UA | | 23-5 | 27-31-11 | SM00001 | | | 9 | D05438J | 10 | DL | | ALL |
| 023 | 16 | | UA | | 29-10 | 33-45-11 | D05438J | | 13 | FL | SP01962 | | | 9 | ALL |
| 024 | 16 | | UA | | 29-10 | 33-45-11 | D05438J | | 14 | FL | SP01964 | | | 9 | ALL |
| 025 | 20 | | UA | | 29-10 | 27-38-11 | D05438J | | 12 | | SP05090 | | | 9 | 157, 167-199, 277-299 |
| 026 | 20 | | UA | | 29-10 | 27-38-11 | D05438J | | 11 | | SP05092 | | | 9 | 157, 167-199, 277-299 |
| A-A | | | | | 0-0 | 27-38-11 | SP02646 | | | 9 | M01145 | | B | | ALL |
| A-B | | | | | 0-0 | 27-38-11 | SP02650 | | | 9 | M01144 | | B | | ALL |
| A-C | | | | | 0-0 | 27-38-11 | SP02654 | | | 9 | M01147 | | B | | ALL |
| A-D | | | | | 0-0 | 27-38-11 | SP02658 | | | 9 | M01146 | | B | | ALL |
| W0503 | 286T0503 | | | PITCH SERVO ACTR, RO SERVO ACTR & STAB POS XMTR R | | | | | | | | | | | |
| 001 | 22 | | PA | | 132-6 | 22-11-22 | D04385J | | 1 | | D04473P | 1 | | | 050-099 |
| 001 | 22 | | PA | | 153-9 | 22-11-22 | D04385J | | 1 | | D04473P | 1 | | | 150-199, 275-299 |
| 002 | 22 | | PA | | 132-6 | 22-11-22 | D04385J | | 25 | | D04473P | 14 | | | 050-099 |
| 002 | 22 | | PA | | 153-9 | 22-11-22 | D04385J | | 25 | | D04473P | 14 | | | 150-199, 275-299 |
| 003 | 22 | | PA | | 132-6 | 22-11-22 | D04385J | | 28 | | D04527P | 3 | | | 050-099 |
| 003 | 22 | | PA | | 153-9 | 22-11-22 | D04385J | | 28 | | D04527P | 3 | | | 150-199, 275-299 |
| 004 | 22 | | PA | | 132-6 | 22-11-22 | D04385J | | 49 | | D04527P | 9 | | | 050-099 |
| 004 | 22 | | PA | | 153-9 | 22-11-22 | D04385J | | 49 | | D04527P | 9 | | | 150-199, 275-299 |
| 005Y | 22 | | PJ | | 153-7 | SPARE | D04385J | | 36 | | D04533P | 9 | | | 150-199, 275-299 |
| 006 | 20 | | PA | | 132-6 | 27-41-21 | D04385J | | 33 | | D04533P | 6 | | | 050-099 |
| 006 | 20 | | PA | | 153-7 | 27-41-21 | D04385J | | 33 | | D04533P | 6 | | | 150-199, 275-299 |
| 007 | 20 | | PA | | 132-6 | 27-41-21 | D04385J | | 34 | | D04533P | 7 | | | 050-099 |
| 007 | 20 | | PA | | 153-7 | 27-41-21 | D04385J | | 34 | | D04533P | 7 | | | 150-199, 275-299 |
| 008Y | 22 | | PJ | | 132-6 | 27-41-21 | D04385J | | 35 | | D04533P | 8 | | | 050-099 |
| 008Y | 22 | | PJ | | 153-7 | 27-41-21 | D04385J | | 35 | | D04533P | 8 | | | 150-199, 275-299 |
| 009Y | 22 | | PJ | | 132-6 | 27-41-21 | D04385J | | 36 | | D04533P | 9 | | | 050-099 |
| 010Y | 22 | | PJ | | 132-6 | 27-41-21 | D04385J | | 37 | | D04533P | 10 | | | 050-099 |
| 010Y | 22 | | PJ | | 153-7 | 27-41-21 | D04385J | | 37 | | D04533P | 10 | | | 150-199, 275-299 |
| 011 | 24 | | PK | | 132-6 | 27-48-11 | D04385J | | 41 | | D04533P | 1 | | | 050-099 |
| 011 | 24 | | PK | | 153-7 | 27-48-11 | D04385J | | 41 | | D04533P | 1 | | | 150-154, 157-164, 167-199, 275-299 |
| 012 | 24 | | PK | | 137-6 | 27-48-11 | D04379J | | 42 | | D04533P | 2 | | | 050 |
| 012 | 24 | | PK | | 135-6 | 27-48-11 | D04379J | | 42 | | D04533P | 2 | | | 051-099 |
| 012 | 24 | | PK | | 153-7 | 27-48-11 | D04385J | | 42 | | D04533P | 2 | | | 150-154, 275-276 |
| 012 | 24 | | PK | | 159-5 | 27-48-11 | D04379J | | 42 | | D04533P | 2 | | | 162-164 |
| 013 | 24 | | PK | | 137-6 | 27-48-11 | D04379J | | 43 | | D04533P | 3 | | | 050 |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|---------|-------|-------------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0503 | 286T0503 | | | PITCH SERVO ACTR, RO SERVO ACTR & STAB POS XMTR R (continued) | | | | | | | | | | | |
| 013 | 24 | | PK | | 135-6 | 27-48-11 | D04379J | | 43 | | D04533P | | 3 | | 051-099 |
| 013 | 24 | | PK | | 153-7 | 27-48-11 | D04385J | | 43 | | D04533P | | 3 | | 150-154, 275-276 |
| 013 | 24 | | PK | | 159-5 | 27-48-11 | D04379J | | 43 | | D04533P | | 3 | | 162-164 |
| 019 | 22 | | PA | | 132-6 | SPARE | D04385J | | 29 | | D04527P | | 4 | | 050-099 |
| 019 | 22 | | PA | | 153-9 | SPARE | D04385J | | 29 | | D04527P | | 4 | | 150-199, 275-299 |
| 023Y | 22 | | PJ | | 132-6 | 27-41-21 | D04385J | | 53 | | D04473P | | 3 | | 050-099 |
| 023Y | 22 | | PJ | | 153-9 | 27-41-21 | D04385J | | 53 | | D04473P | | 3 | | 150-199, 275-299 |
| 201B | 22 | | PB | IA | 132-6 | 22-11-21 | D04385J | | 6 | | D04473P | | 5 | | 050-099 |
| 201B | 22 | | PB | IA | 153-9 | 22-11-21 | D04385J | | 6 | | D04473P | | 5 | | 150-199, 275-299 |
| 201R | 22 | | PB | IA | 0-0 | 22-11-21 | D04385J | | 5 | | D04473P | | 4 | | ALL |
| 202B | 22 | | PB | IB | 132-6 | 22-11-21 | D04385J | | 8 | | D04527P | | 8 | | 050-099 |
| 202B | 22 | | PB | IB | 153-9 | 22-11-21 | D04385J | | 8 | | D04527P | | 8 | | 150-199, 275-299 |
| 202R | 22 | | PB | IB | 0-0 | 22-11-21 | D04385J | | 7 | | D04527P | | 7 | | ALL |
| 203B | 24 | | PL | IC | 132-6 | 27-58-21 | D04385J | | 44 | | D04533P | | 11 | | 050-099 |
| 203B | 24 | | PL | IC | 153-7 | 27-58-21 | D04385J | | 44 | | D04533P | | 11 | | 150-199, 275-299 |
| 203R | 24 | | PL | IC | 0-0 | 27-58-21 | D04385J | | 45 | | D04533P | | 12 | | ALL |
| 204B | 22 | | PB | ID | 132-6 | 22-12-21 | D04385J | | 10 | | D04473P | | 10 | | 050-099 |
| 204B | 22 | | PB | ID | 153-9 | 22-12-21 | D04385J | | 10 | | D04473P | | 10 | | 150-199, 275-299 |
| 204R | 22 | | PB | ID | 0-0 | 22-12-21 | D04385J | | 9 | | D04473P | | 9 | | ALL |
| 205B | 22 | | PB | IE | 132-6 | 22-13-21 | D04385J | | 18 | | D04527P | | 2 | | 050-099 |
| 205B | 22 | | PB | IE | 153-9 | 22-13-21 | D04385J | | 18 | | D04527P | | 2 | | 150-199, 275-299 |
| 205R | 22 | | PB | IE | 0-0 | 22-13-21 | D04385J | | 17 | | D04527P | | 1 | | ALL |
| 206B | 22 | | PB | IF | 132-6 | SPARE | D04385J | | 26 | | D04527P | CAP | Y | | 050-099 |
| 206B | 22 | | PB | IF | 153-9 | SPARE | D04385J | | 26 | | D04527P | CAP | Y | | 150-199, 275-299 |
| 206R | 22 | | PB | IF | 0-0 | SPARE | D04385J | | 2 | | D04527P | CAP | Y | | ALL |
| 207B | 22 | | PB | IG | 132-6 | SPARE | D04385J | | 55 | | D04473P | | 15 | | 050-099 |
| 207B | 22 | | PB | IG | 153-9 | SPARE | D04385J | | 55 | | D04473P | | 15 | | 150-199, 275-299 |
| 207R | 22 | | PB | IG | 0-0 | SPARE | D04385J | | 54 | | D04473P | | 2 | | ALL |
| 301B | 24 | | PM | MA | 132-6 | 27-58-21 | D04385J | | 46 | | D04533P | | 13 | | 050-099 |
| 301B | 24 | | PM | MA | 153-7 | 27-58-21 | D04385J | | 46 | | D04533P | | 13 | | 150-199, 275-299 |
| 301R | 24 | | PM | MA | 0-0 | 27-58-21 | D04385J | | 47 | | D04533P | | 14 | | ALL |
| 301Y | 24 | | PM | MA | 0-0 | 27-58-21 | D04385J | | 48 | | D04533P | | 15 | | ALL |
| 302B | 22 | | PC | MB | 132-6 | 22-12-21 | D04385J | | 12 | | D04473P | | 12 | | 050-099 |
| 302B | 22 | | PC | MB | 153-9 | 22-12-21 | D04385J | | 12 | | D04473P | | 12 | | 150-199, 275-299 |
| 302R | 22 | | PC | MB | 0-0 | 22-12-21 | D04385J | | 11 | | D04473P | | 11 | | ALL |
| 302Y | 22 | | PC | MB | 0-0 | 22-12-21 | D04385J | | 13 | | D04473P | | 13 | | ALL |
| 303B | 22 | | PC | MC | 132-6 | 22-12-21 | D04385J | | 15 | | D04473P | | 7 | | 050-099 |
| 303B | 22 | | PC | MC | 153-9 | 22-12-21 | D04385J | | 15 | | D04473P | | 7 | | 150-199, 275-299 |
| 303R | 22 | | PC | MC | 0-0 | 22-12-21 | D04385J | | 14 | | D04473P | | 6 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0503 | 286T0503 | PITCH SERVO ACTR, RO SERVO ACTR & STAB POS XMTR R (continued) | | | | | | | | | | | | | |
| 303Y | 22 | PC | MC | | 0-0 | 22-12-21 | D04385J | | 16 | | D04473P | | 8 | | ALL |
| 304B | 22 | PC | MD | | 132-6 | 22-13-21 | D04385J | | 20 | | D04527P | | 11 | | 050-099 |
| 304B | 22 | PC | MD | | 153-9 | 22-13-21 | D04385J | | 20 | | D04527P | | 11 | | 150-199, 275-299 |
| 304R | 22 | PC | MD | | 0-0 | 22-13-21 | D04385J | | 19 | | D04527P | | 10 | | ALL |
| 304Y | 22 | PC | MD | | 0-0 | 22-13-21 | D04385J | | 21 | | D04527P | | 12 | | ALL |
| 305B | 22 | PC | ME | | 132-6 | 22-13-21 | D04385J | | 23 | | D04527P | | 14 | | 050-099 |
| 305B | 22 | PC | ME | | 153-9 | 22-13-21 | D04385J | | 23 | | D04527P | | 14 | | 150-199, 275-299 |
| 305R | 22 | PC | ME | | 0-0 | 22-13-21 | D04385J | | 22 | | D04527P | | 13 | | ALL |
| 305Y | 22 | PC | ME | | 0-0 | 22-13-21 | D04385J | | 24 | | D04527P | | 15 | | ALL |
| 307B | 24 | PM | MG | | 157-8 | 27-48-11 | D04379J | | 42 | | D04531P | | 2 | | 155-156, 166 |
| 307B | 24 | PM | MG | | 153-7 | 27-48-11 | D04385J | | 42 | | D04533P | | 2 | | 157, 165, 167-199, 277-299 |
| 307R | 24 | PM | MG | | 0-0 | 27-48-11 | D04379J | | 43 | | D04531P | | 3 | | 155-156, 166 |
| 307R | 24 | PM | MG | | 0-0 | 27-48-11 | D04385J | | 43 | | D04533P | | 3 | | 157, 165, 167-199, 277-299 |
| 307Y | 24 | PM | MG | | 0-0 | 27-48-11 | D04379J | | 41 | | D04531P | | 1 | | 155-156, 166 |
| 307Y | 24 | PM | MG | | 0-0 | 27-48-11 | D04385J | | 4 | | D04533P | | 4 | | 157, 167-199, 277-299 |
| 307Y | 24 | PM | MG | | 0-0 | 27-48-11 | D04385J | | 41 | | D04533P | | 1 | | 165 |
| 70K | 20 | PA | | | 132-6 | 29-11-14 | D04385J | | 52 | | D04527P | | 6 | | 050-099 |
| 70K | 20 | PA | | | 153-9 | 29-11-14 | D04385J | | 52 | | D04527P | | 6 | | 150-199, 275-299 |
| 70M | 20 | PA | | | 132-6 | 29-11-14 | D04385J | | 51 | | D04527P | | 5 | | 050-099 |
| 70M | 20 | PA | | | 153-9 | 29-11-14 | D04385J | | 51 | | D04527P | | 5 | | 150-199, 275-299 |
| W0504 | 286T0504 | R HORIZ STAB-R2-FLT CONT | | | | | | | | | | | | | |
| 001 | 20 | UA | | | 20-4 | 27-23-11 | D05440J | | 1 | | D01866 | | 2 | | ALL |
| 002 | 20 | UA | | | 20-4 | 27-23-11 | D05440J | | 2 | | D01866 | | 3 | | ALL |
| 003 | 20 | UA | | | 20-4 | 27-23-11 | D05440J | | 3 | | D01866 | | 10 | | ALL |
| 004 | 18 | UA | | | 2-10 | 27-23-11 | GD00812 | D.. | N | | D01866 | | 1 | | ALL |
| 005 | 18 | UA | | | 2-10 | 27-23-11 | GD00812 | D.. | N | | D01866 | | 9 | | ALL |
| W0506 | 286T0506 | AIR COND RIGHT PACK & ANTISKID | | | | | | | | | | | | | |
| 001 | 24 | PK | | | 14-3 | 32-31-11 | D04646P | | 1 | | D04650P | | 1 | | ALL |
| 002 | 22 | PA | | | 28-1 | SPARE | D04766P | | 2 | | D04658J | | 2 | | ALL |
| 003 | 22 | PA | | | 28-1 | SPARE | D04766P | | 3 | | D04658J | | 3 | | ALL |
| 010 | 24 | PK | | | 15-0 | SPARE | D05552P | | 25 | | D06076P | CAP | Y | | 050-099 |
| 010 | 24 | PK | | | 13-11 | 21-58-16 | D05552P | | 25 | | D06076P | | 15 | | 150-199, 275-299 |
| 011 | 24 | PK | | | 15-0 | SPARE | D05552P | | 31 | | D06076P | CAP | Y | | 050-099 |
| 011 | 24 | PK | | | 13-11 | 21-58-16 | D05552P | | 31 | | D06076P | | 7 | | 150-199, 275-299 |
| 012 | 24 | PK | | | 14-3 | 32-09-12 | D04650P | | 12 | | D04646P | | 12 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0500
Page 5
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0506 | 286T0506 | | | AIR COND RIGHT PACK & ANTISKID (continued) | | | | | | | | | | | |
| 014 | 24 | | PK | 27-5 | 32-42-11 | D04766P | | 14 | | | D04656J | | 14 | | ALL |
| 018 | 24 | | PK | 21-9 | 21-51-21 | D04650P | | 18 | | | D05552P | | 18 | | ALL |
| 021 | 24 | | PK | 21-9 | 21-51-21 | D04650P | | 21 | | | D05552P | | 21 | | ALL |
| 022 | 24 | | PK | 21-9 | 21-51-21 | D04650P | | 22 | | | D05552P | | 22 | | ALL |
| 023 | 22 | | PA | 21-9 | 21-51-21 | D04650P | | 23 | | | D05552P | | 23 | | ALL |
| 024 | 22 | | PA | 21-9 | 21-51-21 | D04650P | | 24 | | | D05552P | | 24 | | ALL |
| 027 | 22 | | PA | 22-2 | 21-25-21 | D05552P | | 3 | | | D04766P | | 60 | | ALL |
| 028 | 24 | | PK | 13-9 | 21-51-21 | D05552P | | 4 | | | D05612P | | 4 | | ALL |
| 030 | 24 | | PK | 13-9 | 21-51-21 | D05552P | | 6 | | | D05612P | | 6 | | ALL |
| 031 | 24 | | PK | 13-9 | 21-51-21 | D05552P | | 7 | | | D05612P | | 7 | | ALL |
| 032 | 24 | | PK | 13-9 | 21-51-21 | D05552P | | 8 | | | D05612P | | 8 | | ALL |
| 033 | 24 | | PK | 13-9 | 21-51-21 | D05552P | | 9 | | | D05612P | | 9 | | ALL |
| 037 | 22 | | PQ | 19-3 | 21-33-11 | D04650P | | 2 | | | D02366 | | 1 | | ALL |
| 037Z | | | BL | 0-0 | 21-33-11 | D04650P | | DED | | | D02366 | | DED | | ALL |
| 038 | 20 | | PA | 2-1 | 21-33-11 | GD00458 | | D.. | E | | D02366 | | 2 | | ALL |
| 039 | 20 | | PA | 2-1 | 21-33-11 | GD00460 | | S.. | E | | D02366 | | 4 | | ALL |
| 042 | 24 | | PK | 14-3 | 32-41-11 | D04650P | | 3 | | | D04646P | | 3 | | ALL |
| 043 | 24 | | PK | 14-3 | SPARE | D04650P | | 4 | | | D04646P | | 4 | | ALL |
| 044 | 24 | | PK | 14-3 | SPARE | D04650P | | 5 | | | D04646P | | 5 | | 150-199, 275-299 |
| 046 | 24 | | PK | 19-4 | 32-42-12 | D04646P | | 7 | | | D04656J | | 2 | | ALL |
| 047 | 24 | | PK | 19-4 | 32-42-12 | D04646P | | 8 | | | D04656J | | 3 | | ALL |
| 048 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 25 | | | D04656J | | 4 | | ALL |
| 049 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 26 | | | D04656J | | 5 | | ALL |
| 050 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 27 | | | D04656J | | 6 | | ALL |
| 051 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 7 | | | D04656J | | 29 | | ALL |
| 052 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 29 | | | D04656J | | 8 | | ALL |
| 053 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 30 | | | D04656J | | 9 | | ALL |
| 054 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 31 | | | D04656J | | 10 | | ALL |
| 055 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 32 | | | D04656J | | 11 | | ALL |
| 056 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 33 | | | D04656J | | 12 | | ALL |
| 057 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 34 | | | D04656J | | 13 | | ALL |
| 058 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 35 | | | D04656J | | 18 | | ALL |
| 059 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 36 | | | D04656J | | 19 | | ALL |
| 060 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 37 | | | D04656J | | 20 | | ALL |
| 061 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 38 | | | D04656J | | 21 | | ALL |
| 062 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 39 | | | D04656J | | 23 | | ALL |
| 063 | 24 | | PK | 26-11 | 32-42-12 | D04650P | | 40 | | | D04656J | | 24 | | ALL |
| 065 | 24 | | PK | 14-8 | 21-25-21 | D04766P | | 23 | | | D04646P | | 18 | | ALL |
| 066 | 24 | | PK | 22-2 | 21-25-21 | D04766P | | 24 | | | D05552P | | 26 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0506 | 286T0506 | | | AIR COND RIGHT PACK & ANTISKID (continued) | | | | | | | | | | | | | | |
| 067 | 22 | | PA | | 14-8 | 21-25-21 | D04766P | | 25 | | | | D04646P | | 19 | | | ALL |
| 068 | 24 | | PK | | 14-2 | 21-25-21 | D04646P | | 22 | | | | D05552P | | 27 | | | ALL |
| 069 | 24 | | PK | | 14-2 | 21-25-21 | D04646P | | 21 | | | | D05552P | | 28 | | | ALL |
| 070 | 24 | | PK | | 14-2 | 21-25-21 | D04646P | | 20 | | | | D05552P | | 29 | | | ALL |
| 071 | 24 | | PK | | 14-2 | 21-25-21 | D04646P | | 23 | | | | D05552P | | 30 | | | ALL |
| 073 | 24 | | PK | | 17-3 | 29-11-12 | D05612P | | 12 | | | | D05204J | | 12 | | | ALL |
| 075 | 22 | | PA | | 21-9 | SPARE | D05552P | | 13 | | | | D04650P | | 13 | | | ALL |
| 076 | 22 | | PA | | 21-9 | SPARE | D05552P | | 14 | | | | D04650P | | 14 | | | ALL |
| 077 | 20 | | PA | | 14-3 | SPARE | D04646P | | 15 | | | | D04650P | | 15 | | | 150-199, 275-299 |
| 078 | 20 | | PA | | 14-3 | SPARE | D04646P | | 16 | | | | D04650P | | 16 | | | 150-199, 275-299 |
| 079 | 20 | | PA | | 14-3 | SPARE | D04646P | | 17 | | | | D04650P | | 17 | | | 150-199, 275-299 |
| 081 | 20 | | PA | | 15-0 | SPARE | D04766P | | 31 | | | | D05768P | CAP | | Y | | ALL |
| 082 | 20 | | PA | | 27-5 | SPARE | D04766P | | 32 | | | | D04656J | | 30 | | | ALL |
| 083 | 20 | | PA | | 27-5 | SPARE | D04766P | | 33 | | | | D04656J | | 31 | | | ALL |
| 084 | 20 | | PA | | 27-7 | SPARE | D04658J | | 38 | | | | D04650P | | 44 | | | ALL |
| 085 | 20 | | PA | | 27-7 | SPARE | D04658J | | 39 | | | | D04650P | | 45 | | | ALL |
| 087 | 24 | | PK | | 14-2 | 73-21-18 | D04646P | | 10 | | | | D05552P | | 1 | | | ALL |
| 088 | 24 | | PK | | 14-2 | 73-21-18 | D04646P | | 52 | | | | D05552P | | 2 | | | ALL |
| 091 | 24 | | PK | | 13-10 | 29-11-12 | D04650P | | 51 | | | | D05612P | | 21 | | | ALL |
| 092 | 22 | | PA | | 13-10 | 29-11-12 | D04650P | | 52 | | | | D05612P | | 22 | | | ALL |
| 093 | 22 | | PA | | 13-10 | 29-11-12 | D04650P | | 53 | | | | D05612P | | 23 | | | ALL |
| 094 | 22 | | PA | | 13-10 | 29-11-12 | D04650P | | 54 | | | | D05612P | | 24 | | | ALL |
| 096 | 24 | | PK | | 5-2 | 21-51-21 | D04646P | | 33 | | | | D05802J | | 12 | | | 150-199, 275-299 |
| 097 | 24 | | PK | | 5-2 | 21-51-21 | D04646P | | 34 | | | | D05802J | | 13 | | | 150-199, 275-299 |
| 106 | 24 | | PK | | 14-3 | 29-31-11 | D04650P | | 42 | | | | D04646P | | 42 | | | ALL |
| 109 | 24 | | PK | | 14-2 | 21-53-12 | D05552P | | 33 | | | | D04646P | | 38 | | | ALL |
| 110 | 24 | | PK | | 14-2 | 21-53-12 | D05552P | | 34 | | | | D04646P | | 37 | | | ALL |
| 111 | 24 | | PK | | 14-2 | 21-53-12 | D05552P | | 35 | | | | D04646P | | 36 | | | ALL |
| 112 | 24 | | PK | | 14-2 | 21-53-12 | D05552P | | 36 | | | | D04646P | | 35 | | | ALL |
| 113 | 24 | | PK | | 14-2 | 21-53-12 | D05552P | | 37 | | | | D04646P | | 24 | | | ALL |
| 114 | 24 | | PK | | 14-2 | 21-53-12 | D05552P | | 38 | | | | D04646P | | 14 | | | ALL |
| 115 | 24 | | PK | | 14-2 | 21-53-12 | D05552P | | 39 | | | | D04646P | | 2 | | | ALL |
| 116 | 24 | | PK | | 22-2 | 21-53-12 | D05552P | | 40 | | | | D04766P | | 34 | | | ALL |
| 118 | 24 | | PK | | 22-2 | 21-53-12 | D05552P | | 42 | | | | D04766P | | 36 | | | ALL |
| 119 | 24 | | PK | | 22-2 | 21-53-12 | D05552P | | 43 | | | | D04766P | | 37 | | | ALL |
| 120 | 24 | | PK | | 22-2 | 21-53-12 | D05552P | | 44 | | | | D04766P | | 38 | | | ALL |
| 121 | 24 | | PK | | 21-9 | 21-53-12 | D05552P | | 45 | | | | D04650P | | 47 | | | ALL |
| 122 | 24 | | PK | | 14-2 | 21-53-12 | D05552P | | 46 | | | | D04646P | | 39 | | | ALL |
| 123 | 24 | | PK | | 14-2 | 21-53-12 | D05552P | | 47 | | | | D04646P | | 40 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0500
 Page 7
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0506 | 286T0506 | | | AIR COND RIGHT PACK & ANTISKID (continued) | | | | | | | | | | | |
| 124 | 24 | | PK | 14-2 | 21-53-12 | D05552P | | 48 | | | D04646P | 41 | | | ALL |
| 125 | 24 | | PK | 14-2 | 21-53-12 | D05552P | | 49 | | | D04646P | 45 | | | ALL |
| 126 | 24 | | PK | 14-2 | 21-53-12 | D05552P | | 50 | | | D04646P | 46 | | | ALL |
| 127 | 24 | | PK | 14-2 | 21-53-12 | D05552P | | 51 | | | D04646P | 47 | | | ALL |
| 139 | 24 | | PK | 14-4 | 21-58-15 | D04766P | | 40 | | | D05612P | 20 | | | ALL |
| 140 | 24 | | PK | 13-10 | 21-58-15 | D06076P | | 2 | | | D05644P | 7 | | | ALL |
| 142 | 18 | | PA | 18-2 | 21-58-15 | D00544 | | 5 | | | D05644P | 1 | DK | | ALL |
| 145 | 24 | | PK | 13-8 | 21-58-15 | D05612P | | 30 | | | D05644P | 4 | | | ALL |
| 149 | 12 | | PA | 17-7 | 21-58-15 | D00544 | | 3 | | | D06288P | 3 | | | ALL |
| 150 | 12 | | PA | 17-7 | 21-58-15 | D00544 | | 2 | | | D06288P | 2 | | | ALL |
| 151 | 12 | | PA | 17-7 | 21-58-15 | D00544 | | 1 | | | D06288P | 1 | | | ALL |
| 152 | 16 | | PA | 3-0 | 21-58-15 | D00544 | | 7 | | | GD01266 | S.. | E | | ALL |
| 153 | 18 | | PA | 4-4 | 21-58-15 | D00544 | | 6 | | | GD01264 | D.. | 2 | | ALL |
| 157 | 24 | | PK | 22-1 | 21-58-16 | D03064 | | 4 | | | D04766P | 20 | | | ALL |
| 158 | 20 | | PA | 2-10 | 21-58-16 | D03064 | | 5 | | | GD01264 | D.. | 2 | | ALL |
| 159 | 20 | | PA | 2-10 | 21-58-16 | D03064 | | 9 | | | GD01264 | D.. | 2 | | ALL |
| 160 | 20 | | PA | 5-0 | 21-58-16 | D03064 | | 10 | | | GD01264 | S.. | 2 | | ALL |
| 161 | 22 | | PA | 22-1 | 21-58-16 | D03064 | | 11 | | | D04766P | 21 | | | ALL |
| 163 | 22 | | PA | 13-10 | 29-32-11 | D04650P | | 50 | | | D05612P | 31 | | | ALL |
| 167 | 24 | | PK | 14-8 | 21-26-11 | D04766P | | 46 | | | D04646P | 9 | | | ALL |
| 169 | 24 | | PK | 14-0 | 21-26-11 | D04646P | | 6 | | | D05644P | 22 | | | ALL |
| 170 | 24 | | PK | 14-0 | 21-26-11 | D04646P | | 50 | | | D05644P | 17 | | | ALL |
| 171 | 24 | | PK | 14-0 | 21-26-11 | D04646P | | 51 | | | D05644P | 18 | | | ALL |
| 173 | 24 | | PK | 14-0 | 21-26-11 | D04646P | | 53 | | | D05644P | 20 | | | ALL |
| 174 | 24 | | PK | 14-0 | 21-26-11 | D04646P | | 11 | | | D05644P | 21 | | | ALL |
| 175 | 24 | | PK | 22-1 | 21-58-11 | D04766P | | 49 | | | D05644P | 28 | | | ALL |
| 178 | 22 | | PA | 22-1 | 21-58-11 | D04766P | | 52 | | | D05644P | 24 | | | ALL |
| 194 | 24 | | PK | 13-8 | 21-61-11 | D05724P | | 3 | | | D05612P | 38 | | | ALL |
| 195 | 22 | | PA | 13-8 | 21-61-11 | D05724P | | 4 | | | D05612P | 39 | | | ALL |
| 197 | 24 | | PK | 13-8 | 21-61-11 | D05724P | | 6 | | | D05612P | 41 | | | ALL |
| 198 | 24 | | PK | 13-8 | 21-61-11 | D05724P | | 7 | | | D05612P | 42 | | | ALL |
| 199 | 24 | | PK | 13-8 | 21-61-11 | D05724P | | 8 | | | D05612P | 43 | | | ALL |
| 201B | 24 | | PL | A | 20-0 | 32-61-13 | D04658J | 26 | | | D04646P | 26 | | | ALL |
| 201R | 24 | | PL | A | 0-0 | 32-61-13 | D04658J | 25 | | | D04646P | 25 | | | ALL |
| 202B | 24 | | PL | B | 20-0 | 32-61-13 | D04658J | 28 | | | D04646P | 28 | | | ALL |
| 202R | 24 | | PL | B | 0-0 | 32-61-13 | D04658J | 27 | | | D04646P | 27 | | | ALL |
| 203B | 24 | | PL | C | 20-0 | 32-61-13 | D04658J | 30 | | | D04646P | 30 | | | ALL |
| 203R | 24 | | PL | C | 0-0 | 32-61-13 | D04658J | 29 | | | D04646P | 29 | | | ALL |
| 204B | 24 | | PL | D | 20-0 | 32-61-13 | D04658J | 32 | | | D04646P | 32 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 8

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0506 | 286T0506 | | | AIR COND RIGHT PACK & ANTISKID (continued) | | | | | | | | | | | |
| 204R | 24 | | PL | D | 0-0 | 32-61-13 | D04658J | | | | 31 | | | | ALL |
| 205B | 24 | | PL | F | 16-6 | 21-61-11 | D05724P | | | | 10 | | | | ALL |
| 205R | 24 | | PL | F | 0-0 | 21-61-11 | D05724P | | | | 11 | | | | ALL |
| 206B | 24 | | PL | H | 5-5 | 21-61-21 | D05612P | | | | 49 | | | | ALL |
| 206R | 24 | | PL | H | 0-0 | 21-61-21 | D05612P | | | | 50 | | | | ALL |
| 207B | 24 | | PL | K | 5-2 | 21-61-31 | D04646P | | | | 57 | | | | ALL |
| 207R | 24 | | PL | K | 0-0 | 21-61-31 | D04646P | | | | 58 | | | | ALL |
| 208B | 22 | | PB | M | 5-0 | 21-61-51 | D04504J | | | | 38 | | | | ALL |
| 208R | 22 | | PB | M | 0-0 | 21-61-51 | D04504J | | | | 39 | | | | ALL |
| 210B | 24 | | PL | P | 19-8 | 32-09-12 | D04658J | | | | 17 | | | | ALL |
| 210R | 24 | | PL | P | 0-0 | 32-09-12 | D04658J | | | | 16 | | | | ALL |
| 211B | 24 | | PW | R | 19-2 | 32-42-11 | D04656J | | | | 27 | | | | ALL |
| 211R | 24 | | PW | R | 0-0 | 32-42-11 | D04656J | | | | 26 | | | | ALL |
| 211Z | | | | R | 0-0 | 32-42-11 | D04656J | | | | 25 | | | | ALL |
| 212B | 24 | | PL | S | 17-3 | 21-31-21 | D05612P | | | | 60 | | | | ALL |
| 212R | 24 | | PL | S | 0-0 | 21-31-21 | D05612P | | | | 61 | | | | ALL |
| 214B | 24 | | PL | V | 4-11 | 21-61-41 | D05768P | | | | 52 | | | | ALL |
| 214R | 24 | | PL | V | 0-0 | 21-61-41 | D05768P | | | | 53 | | | | ALL |
| 219B | 20 | | PR | IA | 13-9 | 73-21-17 | D05552P | | | | 32 | | | | 050-099 |
| 219B | 20 | | PR | T | 13-9 | 73-21-17 | D05552P | | | | 32 | | | | 150-199, 275-299 |
| 219R | 20 | | PR | IA | 0-0 | 73-21-12 | D05552P | | | | 56 | | | | 050-099 |
| 219R | 20 | | PR | T | 0-0 | 73-21-12 | D05552P | | | | 56 | | | | 150-199, 275-299 |
| 219Z | | | | IA | 0-0 | 73-21-12 | D05552P | | | | 57 | | | | 050-099 |
| 219Z | | | | T | 0-0 | 73-21-12 | D05552P | | | | 57 | | | | 150-199, 275-299 |
| 227B | 24 | | PL | JB | 4-9 | 36-23-21 | D05602P | | | | 6 | | | | ALL |
| 227R | 24 | | PL | JB | 0-0 | 36-23-21 | D05602P | | | | 5 | | | | ALL |
| 231B | 24 | | PW | AE | 22-5 | 36-23-21 | D05802J | | | | 54 | | | | 156-162, 166-199, 277-299 |
| 231R | 24 | | PW | AE | 0-0 | 36-23-21 | D05802J | | | | 53 | | | | 156-162, 166-199, 277-299 |
| 231Z | | | | AE | 0-0 | 36-23-21 | D05802J | | | | 55 | | | | 156-162, 166-199, 277-299 |
| 301B | 24 | | PM | G | 16-6 | 21-61-11 | D05724P | | | | 12 | | | | ALL |
| 301R | 24 | | PM | G | 0-0 | 21-61-11 | D05724P | | | | 13 | | | | ALL |
| 301Y | 24 | | PM | G | 0-0 | 21-61-11 | D05724P | | | | 14 | | | | ALL |
| 302B | 24 | | PM | J | 16-6 | 21-61-21 | D05724P | | | | 25 | | | | ALL |
| 302R | 24 | | PM | J | 0-0 | 21-61-21 | D05724P | | | | 26 | | | | ALL |
| 302Y | 24 | | PM | J | 0-0 | 21-61-21 | D05724P | | | | 27 | | | | ALL |
| 303B | 24 | | PM | L | 16-6 | 21-61-31 | D05724P | | | | 38 | | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0500
Page 9
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0506 | 286T0506 | | | AIR COND RIGHT PACK & ANTISKID (continued) | | | | | | | | | | | | | |
| 303R | 24 | | PM | L | 0-0 | 21-61-31 | D05724P | | 39 | | | | D04504J | 30 | | | ALL |
| 303Y | 24 | | PM | L | 0-0 | 21-61-31 | D05724P | | 40 | | | | D04504J | 31 | | | ALL |
| 304B | 24 | | PX | N | 4-11 | 36-23-21 | D05802J | | 21 | | | | D05768P | 31 | | | ALL |
| 304R | 24 | | PX | N | 0-0 | 36-23-21 | D05802J | | 22 | | | | D05768P | 32 | | | ALL |
| 304Y | 24 | | PX | N | 0-0 | 36-23-21 | D05802J | | 23 | | | | D05768P | 33 | | | ALL |
| 304Z | | | | N | 0-0 | 36-23-21 | D05802J | | 20 | | | | D05768P | 30 | | | ALL |
| 305B | 24 | | PM | W | 16-5 | 21-61-41 | D05724P | | 46 | | | | D05802J | 39 | | | ALL |
| 305R | 24 | | PM | W | 0-0 | 21-61-41 | D05724P | | 47 | | | | D05802J | 40 | | | ALL |
| 305Y | 24 | | PM | W | 0-0 | 21-61-41 | D05724P | | 48 | | | | D05802J | 41 | | | ALL |
| 501 | 24 | | PK | | 16-6 | 21-61-11 | D05724P | | 9 | | | | D04504J | 11 | | | ALL |
| 502 | 24 | | PK | | 13-8 | 21-61-11 | D05724P | | 15 | | | | D05612P | 44 | | | ALL |
| 503 | 24 | | PK | | 5-5 | 21-61-11 | D04504J | | 12 | | | | D05612P | 45 | | | ALL |
| 504 | 24 | | PK | | 13-8 | 21-61-21 | D05724P | | 16 | | | | D05612P | 46 | | | ALL |
| 505 | 24 | | PK | | 13-8 | 21-61-21 | D05724P | | 17 | | | | D05612P | 47 | | | ALL |
| 510 | 24 | | PK | | 5-5 | 21-61-21 | D05612P | | 51 | | | | D04504J | 18 | | | ALL |
| 511 | 22 | | PA | | 13-8 | 21-61-21 | D05724P | | 28 | | | | D05612P | 52 | | | ALL |
| 512 | 24 | | PK | | 5-5 | 21-61-21 | D05612P | | 53 | | | | D04504J | 19 | | | ALL |
| 513 | 24 | | PK | | 14-0 | 21-61-31 | D05724P | | 29 | | | | D04646P | 54 | | | ALL |
| 514 | 24 | | PK | | 14-0 | 21-61-31 | D05724P | | 30 | | | | D04646P | 55 | | | ALL |
| 519 | 24 | | PK | | 5-2 | 21-61-31 | D04646P | | 59 | | | | D04504J | 25 | | | ALL |
| 520 | 22 | | PA | | 14-0 | 21-61-31 | D05724P | | 41 | | | | D04646P | 60 | | | ALL |
| 521 | 24 | | PK | | 5-2 | 21-61-31 | D04646P | | 61 | | | | D04504J | 26 | | | ALL |
| 522 | 24 | | PK | | 5-5 | 21-61-11 | D05612P | | 54 | | | | D04504J | 32 | | | ALL |
| 523 | 24 | | PK | | 5-5 | 21-61-11 | D05612P | | 55 | | | | D04504J | 33 | | | ALL |
| 524 | 24 | | PK | | 5-5 | 21-61-21 | D05612P | | 56 | | | | D04504J | 34 | | | ALL |
| 525 | 24 | | PK | | 5-5 | 21-61-21 | D05612P | | 57 | | | | D04504J | 35 | | | ALL |
| 526 | 24 | | PK | | 5-5 | 21-61-31 | D05612P | | 58 | | | | D04504J | 36 | | | ALL |
| 527 | 24 | | PK | | 5-5 | 21-61-31 | D05612P | | 59 | | | | D04504J | 37 | | | ALL |
| 528 | 24 | | PK | | 25-2 | 33-24-11 | D05204J | | 7 | | | | D04650P | 56 | | | ALL |
| 529 | 24 | | PK | | 27-7 | 33-24-11 | D04658J | | 24 | | | | D04650P | 57 | | | ALL |
| 530 | 24 | | PK | | 14-5 | 21-61-51 | D04766P | | 56 | | | | D05768P | 1 | | | ALL |
| 539 | 22 | | PA | | 13-10 | 36-11-52 | D05768P | | 42 | | | | D05644P | 34 | | | ALL |
| 540 | 22 | | PA | | 14-4 | 36-11-52 | D05764P | | 2 | | | | D05768P | 39 | | | ALL |
| 541 | 22 | | PA | | 21-11 | 36-11-52 | D05764P | | 3 | | | | D05644P | 36 | | | ALL |
| 542 | 24 | | PK | | 21-11 | 36-11-52 | D05764P | | 4 | | | | D05644P | 37 | | | ALL |
| 543 | 24 | | PK | | 16-5 | 36-11-52 | D05766P | | 1 | | | | D04504J | 46 | | | ALL |
| 544 | 18 | | PA | | 5-0 | 36-11-52 | D05768P | | 3 | DK | | | D04504J | 47 | DK | | ALL |
| 545 | 18 | | PA | | 5-0 | 36-11-52 | D05768P | | 25 | DK | | | D04504J | 48 | DK | | ALL |
| 546 | 24 | | PK | | 5-0 | 36-11-52 | D05768P | | 6 | | | | D04504J | 49 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 10

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0506 | 286T0506 | | | AIR COND RIGHT PACK & ANTISKID (continued) | | | | | | | | | | | |
| 547 | 18 | | PA | | 7-0 | SPARE | D05768P | CAP | Y | | D04504J | 54 | DK | | 150-154, 275 |
| 548 | 24 | | PK | | 5-0 | 36-11-52 | D05768P | | 8 | | D04504J | 50 | | | ALL |
| 549 | 24 | | PK | | 4-11 | 36-23-21 | D05768P | | 9 | | D05802J | 18 | | | ALL |
| 550 | 24 | | PK | | 5-0 | 36-11-52 | D05768P | | 10 | | D04504J | 51 | | | ALL |
| 551 | 18 | | PA | | 13-9 | 36-11-52 | D05768P | | 11 | DK | D05766P | 3 | DK | | ALL |
| 552 | 18 | | PA | | 13-9 | 36-11-52 | D05768P | | 12 | DK | D05766P | 2 | DK | | ALL |
| 553 | 24 | | PK | | 13-9 | 36-11-52 | D05768P | | 13 | | D05766P | 4 | | | ALL |
| 555 | 24 | | PK | | 22-2 | 33-16-11 | D05552P | | 61 | | D04766P | 59 | | | ALL |
| 556 | 22 | | PA | | 21-11 | 36-11-62 | D05764P | | 5 | | D05766P | 6 | | | ALL |
| 557 | 24 | | PK | | 14-3 | 36-11-62 | D05764P | | 6 | | D05602P | 13 | | | 050-099, 150-156, 162-166, 275-276 |
| 557 | 24 | | PK | | 21-11 | 36-11-62 | D05764P | | 6 | | D05766P | 7 | | | 157, 167-199, 277-299 |
| 558 | 18 | | PA | | 13-10 | 36-11-62 | D06076P | | 20 | DK | D05766P | 8 | DK | | 050-099 |
| 558 | 22 | | PA | | 13-10 | 36-11-62 | D06076P | | 20 | | D05766P | 8 | | | 150-199, 275-299 |
| 559 | 24 | | PK | | 16-5 | 36-11-62 | D05802J | | 2 | | D05766P | 9 | | | ALL |
| 560 | 18 | | PA | | 13-9 | 36-11-62 | D05768P | | 18 | DK | D05766P | 10 | DK | | 050-099, 150-156, 162-166, 275-276 |
| 560 | 20 | | PA | | 13-9 | 36-11-62 | D05768P | | 18 | | D05766P | 10 | | | 157, 167-199, 277-299 |
| 561 | 24 | | PK | | 13-10 | 36-11-62 | D06076P | | 9 | | D05766P | 11 | | | ALL |
| 562 | 24 | | PK | | 4-11 | 36-11-62 | D05802J | | 5 | | D05768P | 15 | | | ALL |
| 563 | 24 | | PK | | 4-11 | 36-11-62 | D05802J | | 6 | | D05768P | 16 | | | ALL |
| 564 | 18 | | PA | | 7-0 | SPARE | D05802J | | 7 | DK | D05768P | CAP | Y | | 050-099 |
| 566 | 24 | | PK | | 4-11 | 36-11-62 | D05802J | | 9 | | D05768P | 19 | | | ALL |
| 567 | 24 | | PK | | 4-11 | 36-11-62 | D05802J | | 10 | | D05768P | 20 | | | ALL |
| 568 | 24 | | PK | | 4-11 | 36-11-62 | D05802J | | 11 | | D05768P | 21 | | | ALL |
| 569 | 24 | | PV | WS | 13-9 | 73-21-11 | D05552P | | 41 | | D05612P | 18 | | | 050-099, 277-299 |
| 569 | 24 | | PV | WS | 13-9 | 73-21-11 | D05552P | | 41 | | D05612P | 32 | | | 150-199, 275-276 |
| 569Z | | | | WS | 0-0 | 73-21-11 | D05552P | | 59 | | D05612P | 19 | | | 050-099, 277-299 |
| 569Z | | | | WS | 0-0 | 73-21-11 | D05552P | | 59 | | D05612P | 33 | | | 150-199, 275-276 |
| 570 | 24 | | PK | | 4-11 | 36-11-62 | D05802J | | 14 | | D05768P | 23 | | | ALL |
| 571 | 24 | | PK | | 13-10 | 36-11-62 | D06076P | | 17 | | D05766P | 31 | | | ALL |
| 573 | 24 | | PK | | 4-11 | 36-23-21 | D05802J | | 15 | | D05768P | 26 | | | ALL |
| 574 | 24 | | PK | | 4-11 | 36-23-21 | D05802J | | 16 | | D05768P | 27 | | | ALL |
| 575 | 24 | | PK | | 4-11 | 36-23-21 | D05802J | | 17 | | D05768P | 28 | | | ALL |
| 576 | 24 | | PK | | 4-11 | 36-23-21 | D05802J | | 19 | | D05768P | 29 | | | ALL |
| 578 | 22 | | PA | | 13-10 | 36-22-11 | D05644P | | 38 | | D05768P | 34 | | | ALL |
| 584 | 24 | | PK | | 17-5 | 24-22-21 | D05204J | | 13 | | D05768P | 22 | | | ALL |
| 586 | 18 | | PA | | 14-4 | 36-11-52 | D05764P | | 1 | DL | D05768P | 14 | DK | | 050-099, 150-156, 162-166, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 11

Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0506 | 286T0506 | | | AIR COND RIGHT PACK & ANTISKID (continued) | | | | | | | | | | | | | |
| 586 | 18 | | PA | | 21-11 | 36-11-52 | D05764P | 1 | DL | | | | D05766P | 27 | DK | | 157, 167-199, 277-299 |
| 587 | 24 | | PK | | 13-10 | 36-11-52 | D05644P | 35 | | | | | D05768P | 40 | | | ALL |
| 589 | 24 | | PK | | 21-11 | 36-11-52 | D05644P | 25 | | | | | D05764P | 8 | | | ALL |
| 590 | 22 | | PA | | 16-5 | 36-11-52 | D04504J | 7 | | | | | D05766P | 13 | | | ALL |
| 591 | 22 | | PA | | 16-5 | 36-11-52 | D04504J | 8 | | | | | D05766P | 14 | | | ALL |
| 592 | 24 | | PK | | 22-1 | 21-58-11 | D04766P | 45 | | | | | D05644P | 40 | | | ALL |
| 595 | 12 | | PA | | 16-9 | 21-58-15 | D05928P | 1 | | | | | D06288P | 4 | | | ALL |
| 596 | 12 | | PA | | 16-9 | 21-58-15 | D05928P | 2 | | | | | D06288P | 5 | | | ALL |
| 597 | 12 | | PA | | 16-9 | 21-58-15 | D05928P | 3 | | | | | D06288P | 6 | | | ALL |
| 601 | 24 | | PK | | 13-10 | 29-11-12 | D04650P | 58 | | | | | D05612P | 11 | | | ALL |
| 613 | 24 | | PK | | 19-2 | 32-42-11 | D04656J | 28 | | | | | D05768P | 45 | | | ALL |
| 614 | 22 | | PA | | 14-7 | 28-42-11 | D05764P | 11 | | | | | D04646P | 13 | | | ALL |
| 623 | 24 | | PK | | 28-1 | 32-09-21 | D04766P | 22 | | | | | D04658J | 12 | | | ALL |
| 624 | 24 | | PK | | 22-1 | 21-58-11 | D04766P | 35 | | | | | D05644P | 41 | | | ALL |
| 625 | 24 | | PK | | 13-10 | 21-58-16 | D06076P | 8 | | | | | D03064 | 12 | | | ALL |
| 626 | 22 | | PA | | 4-11 | 21-61-11 | D06076P | 3 | | | | | D05802J | 30 | | | ALL |
| 627 | 24 | | PK | | 4-11 | 21-61-21 | D06076P | 4 | | | | | D05802J | 29 | | | ALL |
| 628 | 24 | | PK | | 4-11 | 21-61-31 | D06076P | 5 | | | | | D05802J | 28 | | | ALL |
| 652 | 22 | | PA | | 22-1 | 36-22-11 | D04766P | 55 | | | | | D05644P | 29 | | | ALL |
| 653 | 24 | | PK | | 17-3 | 29-11-12 | D05204J | 14 | | | | | D05612P | 3 | | | ALL |
| 654 | 24 | | PK | | 13-9 | 21-51-13 | D05552P | 5 | | | | | D05612P | 14 | | | ALL |
| 656 | 24 | | PK | | 14-3 | 21-58-14 | D05764P | 9 | | | | | D05612P | 5 | | | ALL |
| 657 | 24 | | PK | | 14-3 | 21-58-14 | D05764P | 10 | | | | | D05612P | 17 | | | ALL |
| 661 | 24 | | PK | | 19-10 | 32-09-12 | D05768P | 49 | | | | | D04658J | 33 | | | ALL |
| 666 | 24 | | PK | | 20-8 | 24-51-52 | D05766P | 15 | | | | | D05204J | 2 | | | ALL |
| 667 | 24 | | PK | | 20-8 | 24-51-52 | D05766P | 16 | | | | | D05204J | 3 | | | ALL |
| 668 | 22 | | PA | | 20-8 | 24-51-52 | D05766P | 17 | | | | | D05204J | 4 | | | 050-099, 150-199 |
| 669 | 22 | | PA | | 20-8 | 24-51-52 | D05766P | 18 | | | | | D05204J | 5 | | | 050-099, 150-199 |
| 673 | 22 | | PQ | C3 | 14-4 | 21-28-11 | D04766P | 5 | | | | | D05602P | 4 | | | 050-099 |
| 673 | 22 | | PA | | 14-4 | 21-28-11 | D04766P | 5 | | | | | D05602P | 4 | | | 150-199, 275-299 |
| 673Z | | | | C3 | 0-0 | 21-28-11 | D04766P | DED | | | | | D05602P | DED | | | 050-099 |
| 674 | 24 | | PV | E | 13-10 | 80-11-11 | D04650P | 19 | | | | | D05612P | 10 | | | ALL |
| 674Z | | | | E | 0-0 | 80-11-11 | D04650P | DED | | | | | D05612P | DED | | | ALL |
| 675 | 24 | | PV | I | 13-10 | 80-11-21 | D04650P | 20 | | | | | D05612P | 25 | | | ALL |
| 675Z | | | | I | 0-0 | 80-11-21 | D04650P | DED | | | | | D05612P | DED | | | ALL |
| 676 | 24 | | PK | | 17-3 | 29-11-31 | D05204J | 6 | | | | | D05612P | 35 | | | ALL |
| 677 | 24 | | PK | | 17-3 | 29-11-31 | D05204J | 8 | | | | | D05612P | 36 | | | ALL |
| 679 | 24 | | PK | | 4-11 | 36-11-62 | D05802J | 25 | | | | | D05768P | 24 | | | ALL |
| 680 | 24 | | PK | | 4-11 | 36-11-62 | D05802J | 24 | | | | | D05768P | 2 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 12

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0506 | 286T0506 | | | AIR COND RIGHT PACK & ANTISKID (continued) | | | | | | | | | | | |
| 681 | 24 | | PK | | 17-3 | 29-11-12 | D05612P | | 2 | | D05204J | | 15 | | ALL |
| 682 | 16 | | PA | | 13-11 | 28-22-11 | D05928P | | 7 | | D05602P | | 1 | | ALL |
| 683 | 16 | | PA | | 13-11 | 28-22-11 | D05928P | | 8 | | D05602P | | 2 | | ALL |
| 684 | 16 | | PA | | 13-11 | 28-22-11 | D05928P | | 9 | | D05602P | | 3 | | ALL |
| 685 | 24 | | PV | AS | 13-10 | 73-21-11 | D06076P | | 10 | | D05766P | | 25 | | 050-099 |
| 685 | 24 | | PV | D5 | 13-10 | 73-21-11 | D06076P | | 10 | | D05766P | | 25 | | 150-199, 275-299 |
| 685Z | | | | AS | 0-0 | 73-21-11 | D06076P | | 16 | | D05766P | | 26 | | 050-099 |
| 685Z | | | | D5 | 0-0 | 73-21-11 | D06076P | | 16 | | D05766P | | 26 | | 150-199, 275-299 |
| 689 | 22 | | PA | | 13-10 | 36-11-52 | D05644P | | 14 | | D05768P | | 38 | | ALL |
| 690 | 22 | | PA | | 13-10 | 21-61-41 | D05768P | | 35 | | D05724P | | 42 | | ALL |
| 691 | 24 | | PK | | 13-10 | 21-61-41 | D05768P | | 36 | | D05724P | | 43 | | ALL |
| 692 | 24 | | PK | | 13-10 | 21-61-41 | D05768P | | 37 | | D05724P | | 44 | | ALL |
| 694 | 24 | | PK | | 4-11 | 21-61-41 | D05768P | | 41 | | D05802J | | 38 | | ALL |
| 695 | 24 | | PK | | 4-11 | 21-61-41 | D05768P | | 44 | | D05802J | | 37 | | ALL |
| 696 | 24 | | PK | | 4-11 | 21-61-41 | D05768P | | 51 | | D05802J | | 36 | | ALL |
| 697 | 24 | | PK | | 4-11 | 21-61-41 | D05768P | | 54 | | D05802J | | 33 | | ALL |
| 698 | 24 | | PK | | 4-11 | 21-61-41 | D05768P | | 55 | | D05802J | | 32 | | ALL |
| 699 | 24 | | PK | | 14-0 | 21-26-11 | D04646P | | 48 | | D05644P | | 32 | | ALL |
| 700 | 24 | | PK | | 14-0 | 21-26-11 | D04646P | | 49 | | D05644P | | 33 | | ALL |
| 702 | 24 | | PK | | 13-11 | SPARE | D06076P | | 11 | | D05552P | | 52 | | 150-199 |
| 703 | 24 | | PK | | 13-11 | 21-58-12 | D06076P | | 12 | | D05552P | | 53 | | ALL |
| 704 | 24 | | PK | | 13-11 | 21-58-12 | D06076P | | 13 | | D05552P | | 54 | | ALL |
| 705 | 24 | | PK | | 13-11 | 21-58-12 | D06076P | | 14 | | D05552P | | 55 | | ALL |
| 710 | 24 | | PK | | 13-10 | 21-58-15 | D06076P | | 6 | | D05644P | | 8 | | ALL |
| 711 | 24 | | PK | | 5-5 | 21-61-11 | D05612P | | 40 | | D04504J | | 1 | | ALL |
| 712 | 24 | | PK | | 5-5 | 21-61-21 | D05612P | | 48 | | D04504J | | 9 | | ALL |
| 713 | 24 | | PK | | 5-2 | 21-61-31 | D04646P | | 56 | | D04504J | | 55 | | ALL |
| 714 | 24 | | PK | | 4-11 | 21-61-41 | D05768P | | 43 | | D05802J | | 26 | | ALL |
| 715 | 24 | | PK | | 16-6 | 21-61-11 | D05724P | | 5 | | D04504J | | 4 | | ALL |
| 716 | 24 | | PK | | 16-6 | 21-61-21 | D05724P | | 18 | | D04504J | | 40 | | ALL |
| 717 | 24 | | PK | | 16-6 | 21-61-31 | D05724P | | 31 | | D04504J | | 42 | | ALL |
| 718 | 24 | | PK | | 16-5 | 21-61-41 | D05724P | | 45 | | D05802J | | 27 | | ALL |
| 719R | 22 | | PH | | 13-10 | 26-18-22 | D05602P | | 7 | | D04650P | | 48 | | ALL |
| 720R | 22 | | PH | | 13-10 | 26-18-22 | D05602P | | 8 | | D04650P | | 49 | | ALL |
| 721 | 22 | | PA | | 13-10 | 36-11-62 | D06076P | | 24 | | D05766P | | 24 | | ALL |
| 722 | 22 | | PA | | 13-10 | 36-11-62 | D06076P | | 23 | | D05766P | | 23 | | ALL |
| 723 | 24 | | PK | | 13-10 | 36-11-62 | D06076P | | 22 | | D05766P | | 22 | | ALL |
| 724 | 24 | | PK | | 13-10 | 36-11-62 | D06076P | | 21 | | D05766P | | 21 | | ALL |
| 725R | 22 | | PH | | 21-7 | 26-18-22 | D04650P | | 9 | | D05766P | | 19 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0500
Page 13
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|-------|---|-------------|---------|-------|------|-------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0506 | 286T0506 | | | AIR COND RIGHT PACK & ANTISKID (continued) | | | | | | | | | | | |
| 726R | 22 | | PH | 21-7 | 26-18-22 | D04650P | | 10 | | | D05766P | | 20 | | ALL |
| 738 | 22 | | PA | 4-11 | 36-23-21 | D05802J | | 42 | | | D06076P | | 18 | | ALL |
| 739 | 22 | | PA | 4-11 | 36-23-21 | D05802J | | 43 | | | D06076P | | 19 | | ALL |
| 740 | 24 | | PK | 13-8 | 36-11-62 | D05766P | | 7 | | | D05602P | | 14 | | 050-099, 150-156, 162-166, 275-276 |
| 743 | 22 | | PA | 14-6 | 21-26-31 | D06076P | | 1 | | | D04766P | | 4 | | ALL |
| 745 | 24 | | PK | 13-8 | 21-61-81 | D05724P | | 20 | | | D05602P | | 10 | | ALL |
| 746 | 24 | | PK | 13-8 | 21-61-81 | D05724P | | 21 | | | D05602P | | 11 | | ALL |
| 752 | 18 | | PA | 14-5 | 36-11-62 | D05768P | | 7 | DK | | D04766P | | 8 | DL | 050-099, 155-156, 162-166, 276 |
| 752 | 18 | | PA | 14-5 | 36-11-52 | D05768P | | 7 | DK | | D04766P | | 8 | DL | 150-154, 275 |
| 752 | 18 | | PA | 15-0 | SPARE | D05768P | | | CAP Y | | D04766P | | 8 | DL | 157, 167-199, 277-299 |
| 754 | 24 | | PK | 14-2 | 73-21-18 | D05552P | | 20 | | | D04646P | | 43 | | 050-099, 280-299 |
| 754 | 24 | | PK | 14-2 | 73-21-11 | D05552P | | 20 | | | D04646P | | 43 | | 150-199, 275-278 |
| 755 | 24 | | PK | 13-9 | 73-21-16 | D05552P | | 10 | | | D05612P | | 15 | | 050-099, 150-199 |
| 768 | 22 | | PA | 4-11 | 36-11-62 | D05802J | | 45 | | | D05768P | | 50 | | ALL |
| 769 | 22 | | PA | 4-11 | 36-11-62 | D05802J | | 46 | | | D05768P | | 17 | | ALL |
| 770 | 22 | | PA | 4-11 | 36-11-62 | D05802J | | 47 | | | D05768P | | 56 | | 050-099, 150-156, 162-166, 275-276 |
| 770 | 22 | | PA | 4-11 | 36-11-62 | D05802J | | 47 | | | D05768P | | 7 | | 157, 167-199, 277-299 |
| 777 | 24 | | PK | 13-10 | 21-26-11 | D05644P | | 26 | | | D05768P | | 60 | | 156-157, 166-199, 277-299 |
| 778 | 24 | | PK | 13-10 | 21-26-11 | D05644P | | 27 | | | D05768P | | 61 | | 156-157, 166-199, 277-299 |
| 779 | 22 | | PA | 14-4 | 30-21-11 | D04766P | | 13 | | | D05612P | | 13 | | 050-099, 150-199 |
| W0507 | 286T0507 | | | CCA L,L WW DISC TO CCA L | | | | | | | | | | | |
| 001 | 18 | | UA | 3-11 | 22-11-12 | GD00097 | | | D.. | N | D00185 | | 1 | | ALL |
| 002 | 20 | | UA | 11-7 | 22-11-12 | D04807P | | 11 | | | D00185 | | 2 | | ALL |
| 003 | 18 | | UA | 3-11 | 22-11-12 | GD00097 | | | D.. | N | D00185 | | 17 | | ALL |
| 004 | 20 | | UA | 11-7 | 22-11-12 | D04807P | | 14 | | | D00185 | | 18 | | ALL |
| 019 | 18 | | UA | 3-11 | 22-11-12 | GD00183 | | | S.. | N | D00185 | | 19 | | ALL |
| 201B | 20 | | UB IA | 11-7 | 22-11-11 | D04807P | | 2 | | | SM00002 | | 9 | | ALL |
| 201R | 20 | | UB IA | 0-0 | 22-11-11 | D04807P | | 1 | | | SM00001 | | 9 | | ALL |
| 202B | 20 | | UB IB | 2-0 | 22-11-11 | SM00002 | | | | 9 | D00185 | | 12 | | ALL |
| 202R | 20 | | UB IB | 0-0 | 22-11-11 | SM00001 | | | | 9 | D00185 | | 13 | | ALL |
| 203B | 20 | | UB IC | 2-0 | 22-11-11 | SM00002 | | | | 9 | D00185 | | 7 | | ALL |
| 203R | 20 | | UB IC | 0-0 | 22-11-11 | SM00001 | | | | 9 | D00185 | | 8 | | ALL |
| 204B | 20 | | UB ID | 11-7 | 22-13-11 | D04807P | | 4 | | | SM00004 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 14

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0507 | 286T0507 | | | CCA L,L WW DISC TO CCA L (continued) | | | | | | | | | | | |
| 204R | 20 | | UB | ID | 0-0 | 22-13-11 | D04807P | | | | SM00003 | | | 9 | ALL |
| 205B | 20 | | UB | IE | 2-0 | 22-13-11 | SM00004 | | 9 | | D00185 | | | 5 | ALL |
| 205R | 20 | | UB | IE | 0-0 | 22-13-11 | SM00003 | | 9 | | D00185 | | | 6 | ALL |
| 206B | 20 | | UB | IF | 2-0 | 22-13-11 | SM00004 | | 9 | | D00185 | | | 3 | ALL |
| 206R | 20 | | UB | IF | 0-0 | 22-13-11 | SM00003 | | 9 | | D00185 | | | 4 | ALL |
| 301B | 20 | | UC | MA | 11-7 | 22-13-11 | D04807P | | 6 | | D00185 | | | 15 | ALL |
| 301R | 20 | | UC | MA | 0-0 | 22-13-11 | D04807P | | 5 | | D00185 | | | 14 | ALL |
| 301Y | 20 | | UC | MA | 0-0 | 22-13-11 | D04807P | | 7 | | D00185 | | | 16 | ALL |
| 302B | 20 | | UC | MB | 11-7 | 22-13-11 | D04807P | | 9 | | D00185 | | | 10 | ALL |
| 302R | 20 | | UC | MB | 0-0 | 22-13-11 | D04807P | | 8 | | D00185 | | | 9 | ALL |
| 302Y | 20 | | UC | MB | 0-0 | 22-13-11 | D04807P | | 10 | | D00185 | | | 11 | ALL |
| W0508 | 286T0508 | | | AIR COND LEFT PACK | | | | | | | | | | | |
| 001 | 20 | | UA | | 12-7 | 21-51-11 | D00670 | | 2 | | D05048P | | | 1 | ALL |
| 002 | 18 | | UA | | 3-11 | 21-51-11 | D00670 | | 1 | | GD00824 | D.. | N | | ALL |
| 003 | 18 | | UA | | 5-0 | 21-52-31 | SM00001 | | 9 | | GD00824 | D.. | N | | ALL |
| 004 | 20 | | UA | | 1-0 | 21-52-31 | D00680 | | B | | SM00001 | | | 9 | ALL |
| 007 | 18 | | UA | | 4-10 | 21-52-41 | D00696 | | 12 | DK | GD02982 | S.. | N | | ALL |
| 008 | 20 | | HA | | 21-8 | 21-61-11 | D05048P | | 20 | | D00698 | | | 1 | ALL |
| 009 | 20 | | HA | | 21-8 | 21-61-11 | D05048P | | 21 | | D00698 | | | 10 | ALL |
| 010 | 20 | | HA | | 4-8 | 21-61-11 | D00698 | | 3 | | GD01696 | A.. | N | | ALL |
| 011 | 20 | | HA | | 4-5 | 21-61-11 | D00698 | | 13 | | GD01698 | S.. | N | | ALL |
| 012 | 20 | | HA | | 21-1 | 21-61-21 | D00710 | | 1 | | D05048P | | | 25 | ALL |
| 013 | 20 | | HA | | 21-1 | 21-61-21 | D00710 | | 10 | | D05048P | | | 26 | ALL |
| 014 | 20 | | HA | | 4-1 | 21-61-21 | D00710 | | 3 | | GD01696 | A.. | N | *2 | ALL |
| 015 | 20 | | HA | | 3-10 | 21-61-21 | D00710 | | 13 | | GD01698 | S.. | N | *2 | ALL |
| 016 | 20 | | HA | | 20-3 | 21-61-31 | D00700 | | 1 | | D05048P | | | 30 | ALL |
| 017 | 20 | | HA | | 20-3 | 21-61-31 | D00700 | | 10 | | D05048P | | | 31 | ALL |
| 018 | 20 | | HA | | 3-3 | 21-61-31 | D00700 | | 3 | | GD01696 | A.. | N | *2 | ALL |
| 019 | 20 | | HA | | 3-0 | 21-61-31 | D00700 | | 13 | | GD01698 | S.. | N | *2 | ALL |
| 023 | 18 | | UA | | 5-0 | 21-52-31 | SM00004 | | 9 | | GD03730 | D.. | N | | 050-099 |
| 023 | 18 | | UA | | 5-3 | 21-52-31 | SM00004 | | 9 | | GD03730 | D.. | N | | 150-199, 275-299 |
| 024 | 20 | | UA | | 1-0 | 21-52-31 | SM00004 | | 9 | | D01338 | B | | | ALL |
| 025 | 18 | | UA | | 5-0 | 21-52-31 | SM00003 | | 9 | | GD03730 | D.. | N | | 050-099 |
| 025 | 18 | | UA | | 6-2 | 21-52-31 | SM00003 | | 9 | | GD03730 | D.. | N | | 150-199, 275-299 |
| 026 | 20 | | UA | | 1-0 | 21-52-31 | SM00003 | | 9 | | D01344 | B | | | ALL |
| 027 | 18 | | UA | | 5-0 | 21-52-31 | SM00002 | | 9 | | GD03730 | D.. | N | | 050-099 |
| 027 | 18 | | UA | | 5-1 | 21-52-31 | SM00002 | | 9 | | GD03730 | D.. | N | | 150-199, 275-299 |
| 028 | 20 | | UA | | 1-0 | 21-52-31 | SM00002 | | 9 | | D01352 | B | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 15

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0508 | 286T0508 | | | AIR COND LEFT PACK (continued) | | | | | | | | | | | | |
| 029 | 20 | | UA | 23-1 | 21-51-11 | D05988P | | 3 | | | D01576 | | 2 | | | ALL |
| 030 | 18 | | UA | 5-0 | 21-51-11 | D01576 | | 1 | | | GD00816 | D.. | N | | | ALL |
| 031 | 18 | | UA | 6-3 | 21-51-12 | D01590 | | 2 | DK | | GD02982 | S.. | N | | | ALL |
| 032 | 18 | | UA | 5-0 | 21-52-31 | SM00005 | | 9 | | | GD03730 | D.. | N | | | 050-099 |
| 032 | 18 | | UA | 5-1 | 21-52-31 | SM00005 | | 9 | | | GD03730 | D.. | N | | | 150-199, 275-299 |
| 033 | 20 | | UA | 1-0 | 21-52-31 | SM00005 | | 9 | | | D02144 | B | | | | ALL |
| 034 | 18 | | UA | 5-0 | 21-52-31 | SM00006 | | 9 | | | GD00864 | D.. | N | | | 050-099 |
| 034 | 18 | | UA | 3-10 | 21-52-31 | SM00006 | | 9 | | | GD00864 | D.. | N | | | 150-199, 275-299 |
| 035 | 20 | | UA | 1-0 | 21-52-31 | SM00006 | | 9 | | | D02152 | B | | | | ALL |
| 036 | 20 | | HA | 11-8 | 36-21-11 | D05988P | | 8 | | | D10144 | | 3 | | | 050-099, 153-199, 275-299 |
| 036 | 20 | | UA | 11-8 | 36-21-11 | D05988P | | 8 | | | D10144 | | 3 | | | 150-152 |
| 037 | 18 | | HL | 2-2 | 36-21-11 | GD00824 | | | D.. | N | D10144 | | 4 | DK | | 050-099, 153-199, 275-299 |
| 037 | 18 | | UA | 2-2 | 36-21-11 | GD00824 | | | D.. | N | D10144 | | 4 | DK | | 150-152 |
| 038 | 18 | | HL | 2-5 | 36-21-11 | GD04684 | | | S.. | N | D10144 | | 5 | DK | | 050-099, 153-199, 275-299 |
| 038 | 18 | | UA | 2-5 | 36-21-11 | GD04684 | | | S.. | N | D10144 | | 5 | DK | | 150-152 |
| 042 | 20 | | HA | 21-0 | 21-61-41 | D05988P | | 16 | | | D10702 | | 1 | | | ALL |
| 043 | 20 | | HA | 21-0 | 21-61-41 | D05988P | | 17 | | | D10702 | | 10 | | | ALL |
| 045 | 20 | | HA | 3-9 | 21-61-41 | D10702 | | 3 | | | GD01696 | A.. | N | | | ALL |
| 046 | 20 | | HA | 3-6 | 21-61-41 | D10702 | | 13 | | | GD01698 | S.. | N | | | ALL |
| 051 | 20 | | HA | 21-11 | 21-61-11 | D00698 | | 2 | | | D05988P | | 24 | | | ALL |
| 052 | 20 | | HA | 21-11 | 21-61-11 | D00698 | | 11 | | | D05988P | | 25 | | | ALL |
| 053 | 20 | | HA | 21-3 | 21-61-21 | D00710 | | 2 | | | D05988P | | 26 | | | ALL |
| 054 | 20 | | HA | 21-3 | 21-61-21 | D00710 | | 11 | | | D05988P | | 27 | | | ALL |
| 055 | 20 | | HA | 20-6 | 21-61-31 | D00700 | | 11 | | | D05988P | | 28 | | | ALL |
| 056 | 20 | | HA | 20-6 | 21-61-31 | D00700 | | 2 | | | D05988P | | 29 | | | ALL |
| 057 | 20 | | HA | 21-0 | 21-61-41 | D10702 | | 2 | | | D05988P | | 30 | | | ALL |
| 058 | 20 | | HA | 21-0 | 21-61-41 | D10702 | | 11 | | | D05988P | | 31 | | | ALL |
| 059 | 20 | | HA | 4-11 | 21-61-61 | D13580 | | 3 | | | GD01696 | A.. | N | | *1 | ALL |
| 060 | 20 | | HA | 22-1 | 21-61-61 | D05988P | | 32 | | | D13580 | | 2 | | | 050-099 |
| 060 | 20 | | HA | 22-1 | 21-61-61 | D13580 | | 2 | | | D05988P | | 32 | | | 150-199, 275-299 |
| 061 | 20 | | HA | 22-1 | 21-61-61 | D05988P | | 33 | | | D13580 | | 11 | | | 050-099 |
| 061 | 20 | | HA | 22-1 | 21-61-61 | D13580 | | 11 | | | D05988P | | 33 | | | 150-199, 275-299 |
| 062 | 20 | | HA | 22-1 | 21-61-61 | D05988P | | 34 | | | D13580 | | 1 | | | 050-099 |
| 062 | 20 | | HA | 22-1 | 21-61-61 | D13580 | | 1 | | | D05988P | | 34 | | | 150-199, 275-299 |
| 063 | 20 | | HA | 22-1 | 21-61-61 | D05988P | | 35 | | | D13580 | | 10 | | | 050-099 |
| 063 | 20 | | HA | 22-1 | 21-61-61 | D13580 | | 10 | | | D05988P | | 35 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 16

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0508 | 286T0508 | | | AIR COND LEFT PACK (continued) | | | | | | | | | | | |
| 064 | 20 | | HA | 4-8 | 21-61-61 | D13580 | | 13 | | GD01698 | S.. | N | *1 | ALL | |
| 065 | 20 | | HA | 4-4 | 21-61-71 | D13582 | | 13 | | GD01698 | S.. | N | *1 | ALL | |
| 066 | 20 | | HA | 21-10 | 21-61-71 | D05988P | | 42 | | D13582 | 10 | | | 050-099 | |
| 066 | 20 | | HA | 21-10 | 21-61-71 | D13582 | | 10 | | D05988P | 42 | | | 150-199, 275-299 | |
| 067 | 20 | | HA | 21-10 | 21-61-71 | D05988P | | 43 | | D13582 | 11 | | | 050-099 | |
| 067 | 20 | | HA | 21-10 | 21-61-71 | D13582 | | 11 | | D05988P | 43 | | | 150-199, 275-299 | |
| 068 | 20 | | HA | 4-7 | 21-61-71 | D13582 | | 3 | | GD01696 | A.. | N | *1 | ALL | |
| 069 | 20 | | HA | 21-10 | 21-61-71 | D05988P | | 44 | | D13582 | 2 | | | 050-099 | |
| 069 | 20 | | HA | 21-10 | 21-61-71 | D13582 | | 2 | | D05988P | 44 | | | 150-199, 275-299 | |
| 070 | 20 | | HA | 21-10 | 21-61-71 | D05988P | | 45 | | D13582 | 1 | | | 050-099 | |
| 070 | 20 | | HA | 21-10 | 21-61-71 | D13582 | | 1 | | D05988P | 45 | | | 150-199, 275-299 | |
| 071 | 20 | | UA | 8-2 | 21-61-81 | D13570 | | 13 | | GD04684 | S.. | N | | ALL | |
| 072 | 20 | | UA | 10-4 | 21-61-81 | D05988P | | 49 | | D13570 | 10 | | | 050-099 | |
| 072 | 20 | | UA | 10-4 | 21-61-81 | D13570 | | 10 | | D05988P | 49 | | | 150-199, 275-299 | |
| 073 | 20 | | UA | 10-4 | 21-61-81 | D05988P | | 50 | | D13570 | 11 | | | 050-099 | |
| 073 | 20 | | UA | 10-4 | 21-61-81 | D13570 | | 11 | | D05988P | 50 | | | 150-199, 275-299 | |
| 074 | 20 | | UA | 10-4 | 21-61-81 | D05988P | | 51 | | D13570 | 2 | | | 050-099 | |
| 074 | 20 | | UA | 10-4 | 21-61-81 | D13570 | | 2 | | D05988P | 51 | | | 150-199, 275-299 | |
| 075 | 20 | | UA | 10-4 | 21-61-81 | D05988P | | 52 | | D13570 | 1 | | | 050-099 | |
| 075 | 20 | | UA | 10-4 | 21-61-81 | D13570 | | 1 | | D05988P | 52 | | | 150-199, 275-299 | |
| 076 | 20 | | UA | 17-8 | 21-61-81 | D13570 | | 3 | | GD00860 | A.. | N | | ALL | |
| 201B | 20 | | UB | B | 12-9 | 21-52-31 | D05048P | 5 | | D00680 | A | | | ALL | |
| 201R | 20 | | UB | B | 0-0 | 21-52-31 | D05048P | 6 | | SM00001 | | 9 | | ALL | |
| 202B | 20 | | UB | F | 22-9 | 21-51-12 | D05048P | 16 | | D00688 | 1 | | | ALL | |
| 202R | 20 | | UB | F | 0-0 | 21-51-12 | D05048P | 17 | | D00688 | 2 | | | ALL | |
| 203B | 20 | | UB | C | 18-10 | 21-52-41 | D05048P | 8 | | D00696 | 2 | | | ALL | |
| 203R | 20 | | UB | C | 0-0 | 21-52-41 | D05048P | 7 | | D00696 | 1 | | | ALL | |
| 204B | 20 | | UB | G | 17-9 | 21-51-12 | D05048P | 18 | | D02824 | 1 | | | ALL | |
| 204R | 20 | | UB | G | 0-0 | 21-51-12 | D05048P | 19 | | D02824 | 2 | | | ALL | |
| 205B | 20 | | HB | ZA | 11-6 | 36-21-11 | D05048P | 51 | | D10144 | 2 | | | 050-099, 153-199, 275-299 | |
| 205B | 20 | | UB | ZA | 11-6 | 36-21-11 | D05048P | 51 | | D10144 | 2 | | | 150-152 | |
| 205R | 20 | | HB | ZA | 0-0 | 36-21-11 | D05048P | 50 | | D10144 | 1 | | | 050-099, 153-199, 275-299 | |
| 205R | 20 | | UB | ZA | 0-0 | 36-21-11 | D05048P | 50 | | D10144 | 1 | | | 150-152 | |
| 206B | 20 | | UB | O | 18-10 | 21-52-41 | D05048P | 44 | | D00696 | 9 | | | ALL | |
| 206R | 20 | | UB | O | 0-0 | 21-52-41 | D05048P | 9 | | D00696 | 8 | | | ALL | |
| 207B | 20 | | UB | Q | 22-10 | 21-52-31 | D05048P | 54 | | D01352 | A | | | 050-099 | |
| 207B | 20 | | UB | IG | 22-10 | 21-52-31 | D05048P | 54 | | D01352 | A | | | 150-199, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W0500
Page 17
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0508 | 286T0508 | | | AIR COND LEFT PACK (continued) | | | | | | | | | | | |
| 207R | 20 | UB | Q | | 0-0 | 21-52-31 | D05048P | | 55 | | SM00002 | | 9 | | 050-099 |
| 207R | 20 | UB | IG | | 0-0 | 21-52-31 | D05048P | | 55 | | SM00002 | | 9 | | 150-199, 275-299 |
| 208B | 20 | UB | R | | 23-7 | 21-52-31 | D05988P | | 9 | | D01344 | A | | | ALL |
| 208R | 20 | UB | R | | 0-0 | 21-52-31 | D05988P | | 10 | | SM00003 | | 9 | | ALL |
| 209B | 20 | UB | S | | 23-3 | 21-52-31 | D05988P | | 13 | | D01338 | A | | | 050-099 |
| 209B | 20 | UB | II | | 23-3 | 21-52-31 | D05988P | | 13 | | D01338 | A | | | 150-199, 275-299 |
| 209R | 20 | UB | S | | 0-0 | 21-52-31 | D05988P | | 14 | | SM00004 | | 9 | | 050-099 |
| 209R | 20 | UB | II | | 0-0 | 21-52-31 | D05988P | | 14 | | SM00004 | | 9 | | 150-199, 275-299 |
| 210B | 20 | UB | T | | 23-7 | 21-51-12 | D05988P | | 2 | | D01590 | | 3 | | ALL |
| 210R | 20 | UB | T | | 0-0 | 21-51-12 | D05988P | | 1 | | D01590 | | 1 | | ALL |
| 211B | 20 | UB | U | | 23-1 | 21-52-31 | D05988P | | 7 | | D02144 | A | | | 050-099 |
| 211B | 20 | UB | IK | | 23-1 | 21-52-31 | D05988P | | 7 | | D02144 | A | | | 150-199, 275-299 |
| 211R | 20 | UB | U | | 0-0 | 21-52-31 | D05988P | | 4 | | SM00005 | | 9 | | 050-099 |
| 211R | 20 | UB | IK | | 0-0 | 21-52-31 | D05988P | | 4 | | SM00005 | | 9 | | 150-199, 275-299 |
| 212B | 20 | UB | V | | 20-11 | 21-52-31 | D05988P | | 11 | | D02152 | A | | | ALL |
| 212R | 20 | UB | V | | 0-0 | 21-52-31 | D05988P | | 12 | | SM00006 | | 9 | | ALL |
| 301B | 20 | HC | D | | 20-2 | 21-51-12 | D05048P | | 10 | | D02792 | | 1 | | ALL |
| 301R | 20 | HC | D | | 0-0 | 21-51-12 | D05048P | | 11 | | D02792 | | 3 | | ALL |
| 301Y | 20 | HC | D | | 0-0 | 21-51-12 | D05048P | | 12 | | D02792 | | 2 | | ALL |
| 302B | 20 | UC | E | | 22-10 | 21-51-12 | D05048P | | 13 | | D00678 | | 2 | | ALL |
| 302R | 20 | UC | E | | 0-0 | 21-51-12 | D05048P | | 14 | | D00678 | | 4 | | ALL |
| 302Y | 20 | UC | E | | 0-0 | 21-51-12 | D05048P | | 15 | | D00678 | | 6 | | ALL |
| 303B | 20 | HC | H | | 21-8 | 21-61-11 | D05048P | | 22 | | D00698 | | 4 | | ALL |
| 303R | 20 | HC | H | | 0-0 | 21-61-11 | D05048P | | 23 | | D00698 | | 5 | | ALL |
| 303Y | 20 | HC | H | | 0-0 | 21-61-11 | D05048P | | 24 | | D00698 | | 12 | | ALL |
| 304B | 20 | HC | J | | 21-1 | 21-61-21 | D00710 | | 4 | | D05048P | | 27 | | ALL |
| 304R | 20 | HC | J | | 0-0 | 21-61-21 | D00710 | | 5 | | D05048P | | 28 | | ALL |
| 304Y | 20 | HC | J | | 0-0 | 21-61-21 | D00710 | | 12 | | D05048P | | 29 | | ALL |
| 305B | 20 | UC | A | | 22-10 | 21-52-11 | D05048P | | 2 | | D00678 | | 1 | | ALL |
| 305R | 20 | UC | A | | 0-0 | 21-52-11 | D05048P | | 3 | | D00678 | | 3 | | ALL |
| 305Y | 20 | UC | A | | 0-0 | 21-52-11 | D05048P | | 4 | | D00678 | | 5 | | ALL |
| 306B | 20 | HC | K | | 20-3 | 21-61-31 | D00700 | | 4 | | D05048P | | 32 | | ALL |
| 306R | 20 | HC | K | | 0-0 | 21-61-31 | D00700 | | 5 | | D05048P | | 33 | | ALL |
| 306Y | 20 | HC | K | | 0-0 | 21-61-31 | D00700 | | 12 | | D05048P | | 34 | | ALL |
| 307B | 20 | HC | MG | | 22-1 | 21-61-61 | D05988P | | 38 | | D13580 | | 4 | | 050-099 |
| 307B | 20 | HC | MG | | 22-1 | 21-61-61 | D13580 | | 4 | | D05988P | | 38 | | 150-199, 275-299 |
| 307R | 20 | HC | MG | | 0-0 | 21-61-61 | D05988P | | 37 | | D13580 | | 5 | | 050-099 |
| 307R | 20 | HC | MG | | 0-0 | 21-61-61 | D13580 | | 5 | | D05988P | | 37 | | 150-199, 275-299 |
| 307Y | 20 | HC | MG | | 0-0 | 21-61-61 | D05988P | | 36 | | D13580 | | 12 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0500

Page 18

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0508 | 286T0508 | | | AIR COND LEFT PACK (continued) | | | | | | | | | | | |
| 307Y | 20 | HC | MG | | 0-0 | 21-61-61 | D13580 | | 12 | | D05988P | | 36 | | 150-199, 275-299 |
| 308B | 20 | HC | MH | | 21-10 | 21-61-71 | D05988P | | 40 | | D13582 | | 4 | | 050-099 |
| 308B | 20 | HC | MC | | 21-10 | 21-61-71 | D13582 | | 4 | | D05988P | | 40 | | 150-199, 275-299 |
| 308R | 20 | HC | MH | | 0-0 | 21-61-71 | D05988P | | 39 | | D13582 | | 5 | | 050-099 |
| 308R | 20 | HC | MC | | 0-0 | 21-61-71 | D13582 | | 5 | | D05988P | | 39 | | 150-199, 275-299 |
| 308Y | 20 | HC | MH | | 0-0 | 21-61-71 | D05988P | | 41 | | D13582 | | 12 | | 050-099 |
| 308Y | 20 | HC | MC | | 0-0 | 21-61-71 | D13582 | | 12 | | D05988P | | 41 | | 150-199, 275-299 |
| 309B | 20 | HC | L | | 20-1 | 21-64-11 | D05048P | | 35 | | D03988 | | 2 | | ALL |
| 309R | 20 | HC | L | | 0-0 | 21-64-11 | D05048P | | 36 | | D03988 | | 3 | | ALL |
| 309Y | 20 | HC | L | | 0-0 | 21-64-11 | D05048P | | 37 | | D03988 | | 1 | | ALL |
| 310B | 20 | HC | M | | 20-5 | 21-64-11 | D05048P | | 38 | | D03990 | | 2 | | ALL |
| 310R | 20 | HC | M | | 0-0 | 21-64-11 | D05048P | | 39 | | D03990 | | 3 | | ALL |
| 310Y | 20 | HC | M | | 0-0 | 21-64-11 | D05048P | | 40 | | D03990 | | 1 | | ALL |
| 311B | 20 | HC | N | | 19-9 | 21-64-11 | D05048P | | 41 | | D03992 | | 2 | | ALL |
| 311R | 20 | HC | N | | 0-0 | 21-64-11 | D05048P | | 42 | | D03992 | | 3 | | ALL |
| 311Y | 20 | HC | N | | 0-0 | 21-64-11 | D05048P | | 43 | | D03992 | | 1 | | ALL |
| 312B | 20 | HC | Y | | 21-0 | 21-61-41 | D05988P | | 20 | | D10702 | | 4 | | ALL |
| 312R | 20 | HC | Y | | 0-0 | 21-61-41 | D05988P | | 19 | | D10702 | | 5 | | ALL |
| 312Y | 20 | HC | Y | | 0-0 | 21-61-41 | D05988P | | 18 | | D10702 | | 12 | | ALL |
| 313B | 20 | HC | Z | | 20-8 | 21-64-11 | D05988P | | 21 | | D10704 | | 2 | | ALL |
| 313R | 20 | HC | Z | | 0-0 | 21-64-11 | D05988P | | 23 | | D10704 | | 3 | | ALL |
| 313Y | 20 | HC | Z | | 0-0 | 21-64-11 | D05988P | | 22 | | D10704 | | 1 | | ALL |
| 314B | 20 | UC | MN | | 10-4 | 21-61-81 | D05988P | | 47 | | D13570 | | 4 | | 050-099 |
| 314B | 20 | UC | MN | | 10-4 | 21-61-81 | D13570 | | 4 | | D05988P | | 47 | | 150-199, 275-299 |
| 314R | 20 | UC | MN | | 0-0 | 21-61-81 | D05988P | | 46 | | D13570 | | 5 | | 050-099 |
| 314R | 20 | UC | MN | | 0-0 | 21-61-81 | D13570 | | 5 | | D05988P | | 46 | | 150-199, 275-299 |
| 314Y | 20 | UC | MN | | 0-0 | 21-61-81 | D05988P | | 48 | | D13570 | | 12 | | 050-099 |
| 314Y | 20 | UC | MN | | 0-0 | 21-61-81 | D13570 | | 12 | | D05988P | | 48 | | 150-199, 275-299 |
| 315B | 20 | HC | MO | | 21-2 | 21-64-11 | D05988P | | 55 | | D12052 | | 2 | | ALL |
| 315R | 20 | HC | MO | | 0-0 | 21-64-11 | D05988P | | 53 | | D12052 | | 3 | | ALL |
| 315Y | 20 | HC | MO | | 0-0 | 21-64-11 | D05988P | | 54 | | D12052 | | 1 | | ALL |
| 316B | 20 | HC | MP | | 20-11 | 21-64-11 | D05048P | | 49 | | D12054 | | 2 | | ALL |
| 316R | 20 | HC | MP | | 0-0 | 21-64-11 | D05048P | | 53 | | D12054 | | 3 | | ALL |
| 316Y | 20 | HC | MP | | 0-0 | 21-64-11 | D05048P | | 52 | | D12054 | | 1 | | ALL |
| 401B | 20 | UD | P | | 18-10 | 21-52-41 | D05048P | | 45 | | D00696 | | 5 | | ALL |
| 401G | 20 | UD | P | | 0-0 | 21-52-41 | D05048P | | 46 | | D00696 | | 4 | | ALL |
| 401R | 20 | UD | P | | 0-0 | 21-52-41 | D05048P | | 47 | | D00696 | | 6 | | ALL |
| 401Y | 20 | UD | P | | 0-0 | 21-52-41 | D05048P | | 48 | | D00696 | | 3 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0500
Page 19 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|----|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0510 | 286T0510 | | | LANDING GEAR POSITION INDICATION & AIR COND LEFT PACK | | | | | | | | | | | | | |
| 002 | 24 | | PK | 30-0 | 32-61-14 | D04676J | | 2 | | | | | D04726P | 2 | | | ALL |
| 003 | 24 | | PK | 30-0 | 32-61-14 | D04676J | | 3 | | | | | D04726P | 3 | | | ALL |
| 008 | 24 | | PK | 30-7 | 21-51-11 | D04502J | | 26 | | | | | D04672P | 14 | | | 150-199, 275-299 |
| 009 | 24 | | PK | 30-7 | 21-51-11 | D04502J | | 27 | | | | | D04672P | 1 | | | 150-199, 275-299 |
| 019 | 24 | | PK | 36-11 | 32-09-11 | D04726P | | 19 | | | | | D04672P | 19 | | | ALL |
| 023 | 24 | | PV | 13-8 | 32-09-11 | D04672P | | 23 | | | | | D04676J | 23 | | | ALL |
| 023Z | | | P | 0-0 | 32-09-11 | D04672P | | | DED | | | | D04676J | DED | | | ALL |
| 024 | 24 | | PV | 13-8 | 32-09-11 | D04672P | | 24 | | | | | D04676J | 24 | | | ALL |
| 024Z | | | Q | 0-0 | 32-09-11 | D04672P | | | DED | | | | D04676J | DED | | | ALL |
| 025 | 24 | | PK | 13-8 | 32-09-11 | D04672P | | 25 | | | | | D04676J | 25 | | | ALL |
| 027 | 24 | | PK | 29-9 | 32-42-11 | D04726P | | 8 | | | | | D04674J | 8 | | | ALL |
| 028R | 22 | | PH | 16-8 | 26-18-11 | D04644P | | 28 | | | | | D04002P | 5 | | | ALL |
| 029R | 22 | | PH | 16-8 | 26-18-11 | D04644P | | 29 | | | | | D04002P | 6 | | | ALL |
| 030R | 22 | | PH | 16-8 | 26-18-21 | D04644P | | 30 | | | | | D04002P | 7 | | | ALL |
| 031R | 22 | | PH | 16-8 | 26-18-21 | D04644P | | 31 | | | | | D04002P | 8 | | | ALL |
| 032R | 22 | | PH | 16-8 | 26-18-31 | D04644P | | 32 | | | | | D04002P | 9 | | | ALL |
| 033R | 22 | | PH | 16-8 | 26-18-31 | D04644P | | 33 | | | | | D04002P | 10 | | | ALL |
| 034R | 22 | | PH | 37-0 | SPARE | D04644P | | 34 | | | | | D04672P | CAP | Y | | 050-099 |
| 035R | 22 | | PH | 37-0 | 26-18-31 | D04644P | | 35 | | | | | D04672P | 35 | | | ALL |
| 040 | 24 | | PK | 28-0 | 32-46-11 | D04644P | | 40 | | | | | D04862J | 1 | | | ALL |
| 041 | 22 | | PA | 28-0 | 32-46-11 | D04644P | | 41 | | | | | D04862J | 2 | | | ALL |
| 061 | 24 | | PK | 13-5 | 32-42-12 | D04674J | | 1 | | | | | D04672P | 16 | | | ALL |
| 062 | 24 | | PK | 13-5 | 32-42-12 | D04674J | | 2 | | | | | D04672P | 17 | | | ALL |
| 063 | 24 | | PK | 37-0 | 28-22-12 | D04644P | | 6 | | | | | D04672P | 18 | | | ALL |
| 064 | 18 | | PA | 37-0 | SPARE | D04726P | | 11 | DL | | | | D04802P | 1 | DK | | 150-199 |
| 067 | 24 | | PK | 37-0 | 21-25-11 | D04644P | | 3 | | | | | D04672P | 32 | | | ALL |
| 068 | 22 | | PA | 37-0 | 21-25-11 | D04644P | | 4 | | | | | D04672P | 33 | | | ALL |
| 069 | 24 | | PK | 25-2 | 21-25-11 | D04644P | | 5 | | | | | D04978P | 1 | | | ALL |
| 070 | 24 | | PK | 30-4 | 21-25-11 | D04978P | | 2 | | | | | D04672P | 36 | | | ALL |
| 071 | 24 | | PK | 30-4 | 21-25-11 | D04978P | | 3 | | | | | D04672P | 37 | | | ALL |
| 072 | 24 | | PK | 30-4 | 21-25-11 | D04978P | | 4 | | | | | D04672P | 38 | | | ALL |
| 073 | 24 | | PK | 17-3 | 21-25-11 | D06732J | | 24 | | | | | D04672P | 43 | | | ALL |
| 082 | 22 | | PA | 36-11 | SPARE | D04726P | | 34 | | | | | D04672P | 41 | | | ALL |
| 084 | 22 | | PA | 30-0 | 52-71-11 | D04726P | | 38 | | | | | D04676J | 38 | | | ALL |
| 085 | 22 | | PA | 30-0 | 52-71-12 | D04726P | | 39 | | | | | D04676J | 39 | | | ALL |
| 086 | 22 | | PA | 30-0 | 52-71-13 | D04726P | | 40 | | | | | D04676J | 40 | | | ALL |
| 087 | 22 | | PA | 30-0 | 52-71-14 | D04726P | | 35 | | | | | D04676J | 41 | | | ALL |
| 088 | 24 | | PK | 30-2 | 32-61-14 | D04644P | | 7 | | | | | D04676J | 19 | | | ALL |
| 090 | 22 | | PA | 29-10 | SPARE | D04644P | | 12 | | | | | D04674J | 9 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0510

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|---------|----------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0510 | 286T0510 | | | LANDING GEAR POSITION INDICATION & AIR COND LEFT PACK (continued) | | | | | | | | | | | |
| 091 | 22 | | PA | | 26-7 | SPARE | D04644P | | 13 | | D04868J | | 14 | | ALL |
| 092 | 22 | | PA | | 26-7 | SPARE | D04644P | | 14 | | D04868J | | 15 | | ALL |
| 093 | 20 | | PA | | 37-0 | SPARE | D04644P | | 15 | | D04672P | CAP | Y | | 150-199, 275-299 |
| 095R | 22 | | PH | | 36-11 | | D04726P | 26-18-11 | 41 | | D04672P | | 27 | | ALL |
| 110 | 24 | | PK | | 37-0 | | D04644P | 33-16-14 | 1 | | D04672P | | 49 | | ALL |
| 111 | 24 | | PK | | 12-2 | | D04002P | 31-51-21 | 11 | | SP00503 | | | S | 050-099 |
| 111 | 24 | | PK | | 28-8 | | D04002P | 31-51-21 | 11 | | D04868J | | 1 | | 150-154, 275 |
| 111 | 24 | | PK | | 12-8 | | D04002P | 31-51-21 | 11 | | SP00503 | | | S | 155-199, 276-299 |
| 112 | 24 | | PK | | 12-2 | | D04002P | 31-51-21 | 12 | | SP00505 | | | S | 050-099 |
| 112 | 24 | | PK | | 28-8 | | D04002P | 31-51-21 | 12 | | D04868J | | 2 | | 150-154, 275 |
| 112 | 24 | | PK | | 12-8 | | D04002P | 31-51-21 | 12 | | SP00505 | | | S | 155-199, 276-299 |
| 113 | 24 | | PK | | 26-5 | | D04726P | 31-51-31 | 1 | | D04868J | | 3 | | ALL |
| 118 | 22 | | PA | | 33-9 | | D04644P | 21-51-11 | 18 | | D06732J | | 38 | | ALL |
| 119 | 22 | | PA | | 17-3 | | D06732J | 21-51-11 | 34 | | D04672P | | 46 | | ALL |
| 120 | 22 | | PA | | 30-7 | | D04502J | 21-51-11 | 22 | | D04672P | | 47 | | ALL |
| 122 | 24 | | PK | | 25-2 | | D04644P | 21-51-11 | 22 | | D04978P | | 10 | | ALL |
| 123 | 24 | | PK | | 25-2 | SPARE | D04644P | | 23 | | D04978P | | 11 | | ALL |
| 124 | 22 | | PA | | 25-2 | | D04644P | 21-25-11 | 2 | | D04978P | | 12 | | ALL |
| 127 | 24 | | PK | | 17-3 | | D06732J | 21-51-11 | 41 | | D04672P | | 52 | | 050-099 |
| 127 | 24 | | PK | | 17-3 | | D04672P | 21-51-11 | 52 | | D06732J | | 41 | | 150-199, 275-299 |
| 128 | 24 | | PK | | 30-4 | | D04672P | 21-51-11 | 53 | | D04978P | | 16 | | ALL |
| 129 | 24 | | PK | | 17-3 | | D04672P | 21-51-11 | 54 | | D06732J | | 36 | | ALL |
| 130 | 24 | | PK | | 17-3 | | D04672P | 21-51-11 | 55 | | D06732J | | 35 | | ALL |
| 131 | 24 | | PK | | 17-3 | | D04672P | 21-51-11 | 57 | | D06732J | | 37 | | ALL |
| 132 | 24 | | PK | | 33-9 | | D04644P | 21-51-11 | 24 | | D06732J | | 39 | | ALL |
| 133 | 24 | | PK | | 33-9 | | D04644P | 21-51-11 | 25 | | D06732J | | 40 | | ALL |
| 134 | 22 | | PA | | 33-9 | | D04644P | 21-51-11 | 26 | | D06732J | | 32 | | ALL |
| 135 | 22 | | PA | | 33-9 | | D04644P | 21-51-11 | 27 | | D06732J | | 33 | | ALL |
| 138 | 24 | | PV | FM | 30-5 | | D04978P | 73-21-11 | 41 | | D04802P | | 26 | | ALL |
| 138Z | | | | FM | 0-0 | | D04978P | 73-21-11 | 40 | | D04802P | | 29 | | ALL |
| 139 | 24 | | PK | | 36-11 | | D04726P | 21-53-11 | 47 | | D04672P | | 59 | | ALL |
| 140 | 24 | | PK | | 17-4 | | D06752J | 21-53-11 | 6 | | D04672P | | 58 | | ALL |
| 143 | 24 | | PK | | 37-0 | | D04726P | 29-31-11 | 50 | | D04802P | | 6 | | ALL |
| 144 | 20 | | PA | | 13-8 | | D04676J | 33-42-11 | 53 | | D04672P | | 60 | | ALL |
| 151 | 24 | | PK | | 25-1 | SPARE | D04726P | | 13 | | D04978P | | 31 | | ALL |
| 152 | 24 | | PK | | 37-0 | | D04726P | 21-58-14 | 15 | | D04802P | | 24 | | ALL |
| 155 | 22 | | PA | | 36-8 | | D05652P | 29-32-11 | 1 | | D04672P | | 56 | | ALL |
| 156 | 24 | | PK | | 25-1 | | D04726P | 21-53-22 | 51 | | D04978P | | 25 | | ALL |
| 158 | 24 | | PK | | 25-1 | | D04726P | 21-53-22 | 53 | | D04978P | | 27 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0510
Page 2
Mar 14/2007



| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|---------|-------|-------------|------|------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0510 | 286T0510 | | | LANDING GEAR POSITION INDICATION & AIR COND LEFT PACK (continued) | | | | | | | | | | | |
| 159 | 24 | | PK | | 25-1 | 21-53-22 | D04726P | | 54 | | D04978P | | 28 | | ALL |
| 160 | 24 | | PK | | 25-1 | 21-53-22 | D04726P | | 55 | | D04978P | | 29 | | ALL |
| 161 | 24 | | PK | | 25-1 | 21-53-22 | D04726P | | 56 | | D04978P | | 30 | | ALL |
| 164 | 24 | | PK | | 30-5 | 21-58-12 | D04978P | | 8 | | D04802P | | 16 | | ALL |
| 165 | 24 | | PK | | 30-5 | 21-58-12 | D04978P | | 14 | | D04802P | | 17 | | ALL |
| 166 | 24 | | PK | | 30-5 | 21-58-12 | D04978P | | 37 | | D04802P | | 18 | | ALL |
| 167 | 24 | | PK | | 36-9 | 21-58-12 | D05652P | | 2 | | D04802P | | 19 | | ALL |
| 168 | 24 | | PK | | 36-9 | 21-58-12 | D05652P | | 3 | | D04802P | | 20 | | ALL |
| 169 | 24 | | PK | | 30-5 | 21-58-12 | D04978P | | 13 | | D04802P | | 22 | | ALL |
| 175 | 24 | | PK | | 30-7 | 36-23-11 | D04502J | | 11 | | D04672P | | 8 | | ALL |
| 176 | 24 | | PK | | 30-8 | 36-23-11 | D04502J | | 6 | | D04802P | | 31 | | ALL |
| 177 | 24 | | PK | | 30-8 | 36-23-11 | D04502J | | 7 | | D04802P | | 32 | | ALL |
| 178 | 24 | | PK | | 30-8 | 36-23-11 | D04502J | | 8 | | D04802P | | 33 | | ALL |
| 179 | 24 | | PK | | 30-8 | 36-23-11 | D04502J | | 9 | | D04802P | | 34 | | ALL |
| 180 | 24 | | PK | | 30-8 | 36-23-11 | D04502J | | 10 | | D04802P | | 35 | | ALL |
| 183 | 24 | | PK | | 13-9 | 24-22-11 | D04676J | | 1 | | D04802P | | 7 | | ALL |
| 185 | 24 | | PK | | 29-9 | 32-42-11 | D04726P | | 20 | | D04674J | | 3 | | ALL |
| 186 | 24 | | PK | | 37-0 | 21-58-13 | D04644P | | 10 | | D04672P | | 9 | | ALL |
| 188R | 22 | | PH | | 36-11 | 26-18-11 | D04726P | | 21 | | D04672P | | 31 | | ALL |
| 193 | 24 | | PK | | 25-2 | 21-25-11 | D04644P | | 19 | | D04978P | | 7 | | ALL |
| 194 | 24 | | PK | | 30-5 | 21-58-12 | D04978P | | 48 | | D04802P | | 13 | | ALL |
| 196 | 24 | | PK | | 29-6 | 32-42-12 | D05652P | | 4 | | D04674J | | 4 | | ALL |
| 197 | 24 | | PK | | 29-6 | 32-42-12 | D05652P | | 5 | | D04674J | | 5 | | ALL |
| 198 | 24 | | PK | | 29-6 | 32-42-12 | D05652P | | 6 | | D04674J | | 6 | | ALL |
| 199 | 24 | | PK | | 29-6 | 32-42-12 | D05652P | | 7 | | D04674J | | 7 | | ALL |
| 201B | 24 | | PL | A | 13-8 | 32-61-13 | D04676J | | 28 | | D04672P | | 3 | | ALL |
| 201R | 24 | | PL | A | 0-0 | 32-61-13 | D04676J | | 27 | | D04672P | | 2 | | ALL |
| 202B | 24 | | PL | B | 13-8 | 32-61-13 | D04676J | | 30 | | D04672P | | 5 | | ALL |
| 202R | 24 | | PL | B | 0-0 | 32-61-13 | D04676J | | 29 | | D04672P | | 4 | | ALL |
| 203B | 24 | | PL | C | 13-8 | 32-61-13 | D04676J | | 32 | | D04672P | | 7 | | ALL |
| 203R | 24 | | PL | C | 0-0 | 32-61-13 | D04676J | | 31 | | D04672P | | 6 | | ALL |
| 204B | 24 | | PL | D | 13-8 | 32-61-13 | D04676J | | 34 | | D04672P | | 13 | | ALL |
| 204R | 24 | | PL | D | 0-0 | 32-61-13 | D04676J | | 33 | | D04672P | | 12 | | ALL |
| 206B | 24 | | PL | F | 13-8 | 32-09-11 | D04676J | | 11 | | D04672P | | 11 | | ALL |
| 206R | 24 | | PL | F | 0-0 | 32-09-11 | D04676J | | 10 | | D04672P | | 10 | | ALL |
| 208B | 24 | | PL | M | 30-7 | 21-51-11 | D04672P | | 44 | | D04502J | | 21 | | ALL |
| 208R | 24 | | PL | M | 0-0 | 21-51-11 | D04672P | | 45 | | D04502J | | 20 | | ALL |
| 209B | 24 | | PL | N | 29-6 | SPARE | D05652P | | 10 | | D04674J | | 10 | | ALL |
| 209R | 24 | | PL | N | 0-0 | SPARE | D05652P | | 11 | | D04674J | | 11 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0510

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0510 | 286T0510 | | | LANDING GEAR POSITION INDICATION & AIR COND LEFT PACK (continued) | | | | | | | | | | | |
| 214B | 20 | PR | IA | | 30-5 | 73-21-17 | D04978P | | 32 | | D04802P | | 27 | | 050-099 |
| 214B | 20 | PR | IN | | 30-5 | 73-21-17 | D04978P | | 32 | | D04802P | | 27 | | 150-199 |
| 214B | 20 | PR | E | | 30-5 | 73-21-17 | D04978P | | 32 | | D04802P | | 27 | | 275-299 |
| 214R | 20 | PR | IA | | 0-0 | 73-21-12 | D04978P | | 55 | | D04802P | | 21 | | 050-099 |
| 214R | 20 | PR | IN | | 0-0 | 73-21-12 | D04978P | | 55 | | D04802P | | 21 | | 150-199 |
| 214R | 20 | PR | E | | 0-0 | 73-21-12 | D04978P | | 55 | | D04802P | | 21 | | 275-299 |
| 214Z | | | IA | | 0-0 | 73-21-12 | D04978P | | 54 | | D04802P | | 28 | | 050-099 |
| 214Z | | | IN | | 0-0 | 73-21-12 | D04978P | | 54 | | D04802P | | 28 | | 150-199 |
| 214Z | | | E | | 0-0 | 73-21-12 | D04978P | | 54 | | D04802P | | 28 | | 275-299 |
| 215B | 24 | PL | IO | | 27-3 | 21-61-51 | D04502J | | 24 | | D06732J | | 2 | | 050-099 |
| 215B | 24 | PL | IO | | 27-3 | 21-61-51 | D06732J | | 2 | | D04502J | | 24 | | 150-199, 275-299 |
| 215R | 24 | PL | IO | | 0-0 | 21-61-51 | D04502J | | 25 | | D06732J | | 3 | | 050-099 |
| 215R | 24 | PL | IO | | 0-0 | 21-61-51 | D06732J | | 3 | | D04502J | | 25 | | 150-199, 275-299 |
| 216B | 24 | PL | IP | | 33-9 | 21-61-61 | D04644P | | 45 | | D06732J | | 7 | | ALL |
| 216R | 24 | PL | IP | | 0-0 | 21-61-61 | D04644P | | 46 | | D06732J | | 8 | | ALL |
| 217B | 24 | PL | IQ | | 33-9 | 21-61-61 | D04644P | | 47 | | D06732J | | 9 | | ALL |
| 217R | 24 | PL | IQ | | 0-0 | 21-61-61 | D04644P | | 48 | | D06732J | | 10 | | ALL |
| 218B | 24 | PL | IR | | 33-9 | 21-61-71 | D04644P | | 49 | | D06732J | | 14 | | ALL |
| 218R | 24 | PL | IR | | 0-0 | 21-61-71 | D04644P | | 50 | | D06732J | | 13 | | ALL |
| 219B | 24 | PL | IS | | 33-9 | 21-61-71 | D04644P | | 52 | | D06732J | | 11 | | ALL |
| 219R | 24 | PL | IS | | 0-0 | 21-61-71 | D04644P | | 51 | | D06732J | | 12 | | ALL |
| 222B | 24 | PL | IV | | 30-8 | 36-23-11 | D04802P | | 30 | | D04502J | | 13 | | ALL |
| 222R | 24 | PL | IV | | 0-0 | 36-23-11 | D04802P | | 14 | | D04502J | | 12 | | ALL |
| 303B | 24 | PX | K | | 30-8 | 36-23-11 | D04502J | | 17 | | D04802P | | 37 | | ALL |
| 303R | 24 | PX | K | | 0-0 | 36-23-11 | D04502J | | 18 | | D04802P | | 38 | | ALL |
| 303Y | 24 | PX | K | | 0-0 | 36-23-11 | D04502J | | 19 | | D04802P | | 39 | | ALL |
| 303Z | | | K | | 0-0 | 36-23-11 | D04502J | | 16 | | D04802P | | 36 | | ALL |
| 306B | 24 | PM | MF | | 33-9 | 21-61-61 | D04644P | | 42 | | D06732J | | 4 | | ALL |
| 306R | 24 | PM | MF | | 0-0 | 21-61-61 | D04644P | | 43 | | D06732J | | 5 | | ALL |
| 306Y | 24 | PM | MF | | 0-0 | 21-61-61 | D04644P | | 44 | | D06732J | | 6 | | ALL |
| 307B | 24 | PM | MG | | 33-9 | 21-61-71 | D04644P | | 53 | | D06732J | | 15 | | ALL |
| 307R | 24 | PM | MG | | 0-0 | 21-61-71 | D04644P | | 54 | | D06732J | | 16 | | ALL |
| 307Y | 24 | PM | MG | | 0-0 | 21-61-71 | D04644P | | 55 | | D06732J | | 17 | | ALL |
| 308B | 24 | PM | MH | | 33-8 | 21-61-81 | D04726P | | 31 | | D06752J | | 1 | | ALL |
| 308R | 24 | PM | MH | | 0-0 | 21-61-81 | D04726P | | 32 | | D06752J | | 2 | | ALL |
| 308Y | 24 | PM | MH | | 0-0 | 21-61-81 | D04726P | | 33 | | D06752J | | 3 | | ALL |
| 500R | 22 | PH | | | 36-11 | 26-18-12 | D04726P | | 9 | | D04672P | | 29 | | ALL |
| 501R | 22 | PH | | | 36-11 | 26-18-12 | D04726P | | 10 | | D04672P | | 28 | | ALL |
| 502R | 22 | PH | | | 25-2 | 26-18-12 | D04644P | | 36 | | D04978P | | 42 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0510
 Page 4
 Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0510 | 286T0510 | | | LANDING GEAR POSITION INDICATION & AIR COND LEFT PACK (continued) | | | | | | | | | | | | |
| 503R | 22 | | PH | 25-2 | 26-18-12 | D04644P | | 37 | | | D04978P | | 43 | | ALL | |
| 504R | 22 | | PH | 27-4 | 26-18-12 | D04978P | | 44 | | | D04002P | | 3 | | ALL | |
| 513 | 24 | | PK | 33-9 | 21-61-51 | D04644P | | 9 | | | D06732J | | 1 | | ALL | |
| 514 | 24 | | PK | 33-9 | 21-61-61 | D04644P | | 11 | | | D06732J | | 19 | | ALL | |
| 515 | 24 | | PK | 33-9 | 21-61-71 | D04644P | | 21 | | | D06732J | | 18 | | ALL | |
| 516 | 24 | | PK | 33-7 | 21-26-31 | D04726P | | 26 | | | D06732J | | 20 | | 050-099 | |
| 516 | 24 | | PK | 33-7 | 21-26-31 | D06732J | | 20 | | | D04726P | | 26 | | 150-199, 275-299 | |
| 517 | 24 | | PK | 33-7 | 21-26-31 | D04726P | | 27 | | | D06732J | | 21 | | 050-099 | |
| 517 | 24 | | PK | 33-7 | 21-26-31 | D06732J | | 21 | | | D04726P | | 27 | | 150-199, 275-299 | |
| 518 | 24 | | PK | 33-7 | 21-28-11 | D06732J | | 22 | | | D04726P | | 16 | | ALL | |
| 520 | 24 | | PK | 33-7 | 21-43-11 | D04726P | | 29 | | | D06732J | | 30 | | 050-099 | |
| 520 | 24 | | PK | 33-7 | 21-43-11 | D06732J | | 30 | | | D04726P | | 29 | | 150-199, 275-299 | |
| 521 | 24 | | PK | 33-7 | 21-43-11 | D04726P | | 28 | | | D06732J | | 31 | | 050-099 | |
| 521 | 24 | | PK | 33-7 | 21-43-11 | D06732J | | 31 | | | D04726P | | 28 | | 150-199, 275-299 | |
| 522 | 24 | | PK | 17-4 | 21-43-11 | D04802P | | 4 | | | D06732J | | 29 | | ALL | |
| 523 | 24 | | PK | 27-0 | 21-51-11 | D04978P | | 20 | | | D06732J | | 44 | | 050-099 | |
| 523 | 24 | | PK | 27-0 | 21-51-11 | D06732J | | 44 | | | D04978P | | 20 | | 150-199, 275-299 | |
| 524 | 24 | | PK | 27-0 | 21-51-11 | D04978P | | 22 | | | D06732J | | 45 | | 050-099 | |
| 524 | 24 | | PK | 27-0 | 21-51-11 | D06732J | | 45 | | | D04978P | | 22 | | 150-199, 275-299 | |
| 525 | 24 | | PK | 27-0 | 21-51-11 | D04978P | | 21 | | | D06732J | | 46 | | 050-099 | |
| 525 | 24 | | PK | 27-0 | 21-51-11 | D06732J | | 46 | | | D04978P | | 21 | | 150-199, 275-299 | |
| 526 | 24 | | PK | 27-0 | 21-51-11 | D04978P | | 33 | | | D06732J | | 47 | | 050-099 | |
| 526 | 24 | | PK | 27-0 | 21-51-11 | D06732J | | 47 | | | D04978P | | 33 | | 150-199, 275-299 | |
| 527 | 24 | | PK | 27-0 | 21-51-11 | D04978P | | 36 | | | D06732J | | 48 | | 050-099 | |
| 527 | 24 | | PK | 27-0 | 21-51-11 | D06732J | | 48 | | | D04978P | | 36 | | 150-199, 275-299 | |
| 528 | 24 | | PK | 27-0 | 21-51-11 | D04978P | | 17 | | | D06732J | | 49 | | 050-099 | |
| 528 | 24 | | PK | 27-0 | 21-51-11 | D06732J | | 49 | | | D04978P | | 17 | | 150-199, 275-299 | |
| 529 | 24 | | PK | 27-0 | 21-51-11 | D04978P | | 18 | | | D06732J | | 50 | | 050-099 | |
| 529 | 24 | | PK | 27-0 | 21-51-11 | D06732J | | 50 | | | D04978P | | 18 | | 150-199, 275-299 | |
| 530 | 24 | | PK | 27-0 | 21-51-11 | D04978P | | 9 | | | D06732J | | 51 | | 050-099 | |
| 530 | 24 | | PK | 27-0 | 21-51-11 | D06732J | | 51 | | | D04978P | | 9 | | 150-199, 275-299 | |
| 531 | 24 | | PK | 27-0 | 21-51-11 | D04978P | | 15 | | | D06732J | | 52 | | 050-099 | |
| 531 | 24 | | PK | 27-0 | 21-51-11 | D06732J | | 52 | | | D04978P | | 15 | | 150-199, 275-299 | |
| 532 | 24 | | PK | 27-0 | 21-51-11 | D04978P | | 23 | | | D06732J | | 53 | | 050-099 | |
| 532 | 24 | | PK | 27-0 | 21-51-11 | D06732J | | 53 | | | D04978P | | 23 | | 150-199, 275-299 | |
| 533 | 24 | | PK | 27-0 | 21-51-11 | D04978P | | 6 | | | D06732J | | 54 | | 050 | |
| 533 | 24 | | PK | 27-0 | SPARE | D04978P | | 6 | | | D06732J | | 54 | | 051-099 | |
| 533 | 24 | | PK | 27-0 | 21-51-11 | D06732J | | 54 | | | D04978P | | 6 | | 150-154, 275-276 | |
| 533 | 24 | | PK | 27-0 | SPARE | D06732J | | 54 | | | D04978P | | 6 | | 155-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W0510

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|-----------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0510 | 286T0510 | | | LANDING GEAR POSITION INDICATION & AIR COND LEFT PACK (continued) | | | | | | | | | | | |
| 534 | 24 | | PK | 27-0 | 21-51-11 | D04978P | 34 | | | D06732J | 55 | | | 050-099 | |
| 534 | 24 | | PK | 27-0 | 21-51-11 | D06732J | 55 | | | D04978P | 34 | | | 150-199, 275-299 | |
| 535 | 24 | | PK | 17-3 | 21-58-16 | D04672P | 34 | | | D06732J | 43 | | | ALL | |
| 536 | 24 | | PK | 33-8 | 21-61-81 | D04726P | 30 | | | D06752J | 4 | | | ALL | |
| 544 | 24 | | PK | 27-0 | 21-51-11 | D04978P | 5 | | | D06732J | 25 | | | 050-099 | |
| 544 | 24 | | PK | 27-0 | 21-51-11 | D06732J | 25 | | | D04978P | 5 | | | 150-199, 275-299 | |
| 548 | 24 | | PK | 33-7 | 21-61-81 | D04726P | 4 | | | D06732J | 27 | | | ALL | |
| 549 | 24 | | PK | 33-7 | 21-61-81 | D04726P | 5 | | | D06732J | 26 | | | ALL | |
| 550 | 22 | | PA | 6-10 | 21-66-11 | D06752J | 10 | | | D04676J | 5 | | | 050-099, 162-199 | |
| 551 | 24 | | PK | 27-1 | 73-21-15 | D04978P | 49 | | | D06752J | 9 | | | ALL | |
| 552 | 22 | | PA | 6-10 | 21-66-11 | D06752J | 11 | | | D04676J | 6 | | | 050-099, 162-199 | |
| 553 | 22 | | PA | 6-10 | 21-66-11 | D06752J | 12 | | | D04676J | 7 | | | 050-099, 162-199 | |
| 554 | 22 | | PA | 36-8 | 21-66-21 | D05652P | 8 | | | D04672P | 15 | | | 050-099, 162-199 | |
| 555 | 22 | | PA | 6-10 | 21-66-21 | D06752J | 5 | | | D04676J | 4 | | | 050-099 | |
| 555 | 22 | | PA | 6-10 | 21-66-21 | D04676J | 4 | | | D06752J | 5 | | | 162-199 | |
| 556 | 22 | | PA | 17-4 | 21-66-31 | D06752J | 7 | | | D04672P | 30 | | | 050-099 | |
| 556 | 22 | | PA | 17-4 | 21-66-31 | D04672P | 30 | | | D06752J | 7 | | | 150, 152-199 | |
| 557 | 22 | | PA | 6-10 | 21-66-41 | D06752J | 8 | | | D04676J | 8 | | | 050-099, 150, 152-199 | |
| 558 | 22 | | PA | 30-5 | 21-66-11 | D04802P | 5 | | | D04978P | 53 | | | 050-099, 162-199 | |
| 701 | 16 | | PA | 37-0 | 33-42-11 | D04644P | 20 | FL | | D04672P | 20 | FM | | ALL | |
| 702 | 16 | | PA | 37-0 | 33-42-11 | D04644P | 58 | FL | | D04672P | 48 | FM | | ALL | |
| 703 | 20 | | PA | 37-0 | 33-42-21 | D04644P | 56 | | | D04672P | 22 | | | 050-099 | |
| 703 | 18 | | PA | 37-0 | 33-42-21 | D04644P | 56 | DL | | D04672P | 22 | DK | | 150-199, 275-299 | |
| 704 | 20 | | PA | 37-0 | 33-42-21 | D04644P | 57 | | | D04672P | 42 | | | 050-099 | |
| 704 | 18 | | PA | 37-0 | 33-42-21 | D04644P | 57 | DL | | D04672P | 42 | DK | | 150-199, 275-299 | |
| 705 | 24 | | PK | 30-4 | 21-58-11 | D04978P | 26 | | | D04672P | 26 | | | ALL | |
| 707 | 24 | | PK | 30-7 | 21-51-11 | D04502J | 23 | | | D04672P | 21 | | | ALL | |
| 708 | 24 | | PK | 17-3 | 21-51-11 | D06732J | 42 | | | D04672P | 40 | | | ALL | |
| 709 | 24 | | PK | 13-8 | 33-16-14 | D04672P | 50 | | | D04676J | 13 | | | ALL | |
| 711 | 20 | | PA | 13-8 | 25-31-21 | D04672P | 61 | | | D04676J | 54 | | | 050-099, 150-199 | |
| 711 | 18 | | PA | 13-8 | 25-31-21 | D04672P | 61 | DK | | D04676J | 54 | DK | | 275-299 | |
| 712 | 22 | | PA | 37-0 | 52-11-12 | D04726P | 25 | | | D04802P | 25 | | | 050-099, 150-199 | |
| 712 | 20 | | PA | 37-0 | 52-11-12 | D04726P | 25 | | | D04802P | 25 | | | 275-299 | |
| 713 | 24 | | PV | 13-9 | 32-09-11 | D04802P | 10 | | | D04676J | 42 | | | ALL | |
| 713Z | | | R | 0-0 | 32-09-11 | D04802P | DED | | | D04676J | DED | | | ALL | |
| 714 | 24 | | PK | 13-9 | 32-09-11 | D04802P | 11 | | | D04676J | 47 | | | ALL | |
| 715 | 24 | | PK | 13-9 | 32-09-11 | D04802P | 12 | | | D04676J | 48 | | | ALL | |
| 716 | 18 | | PA | 13-8 | 25-31-31 | D04676J | 4 | DK | | D04672P | 39 | DK | | 277-299 | |
| 718 | 24 | | PK | 37-1 | SPARE | D04644P | CAP | Y | | D04802P | CAP | Y | | 051-099, 150-154 | |

WIRE LIST

D280T132

91-21-11
Section W0510
Page 6
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-----|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0510 | 286T0510 | | | LANDING GEAR POSITION INDICATION & AIR COND LEFT PACK (continued) | | | | | | | | | | | | | |
| 718 | 24 | | PK | 37-1 | 21-44-21 | D04644P | | 59 | | | | | D04802P | | 2 | | 275-276 |
| 719 | 24 | | PK | 37-1 | SPARE | D04644P | | | CAP | Y | | | D04802P | | CAP | Y | 051-099, 150-154 |
| 719 | 24 | | PK | 37-1 | 21-44-21 | D04644P | | 8 | | | | | D04802P | | 3 | | 275-276 |
| 803 | 22 | | PA | 20-3 | SPARE | D04644P | | 16 | | | | | D04502J | | 14 | | ALL |
| 804 | 22 | | PA | 20-3 | SPARE | D04644P | | 17 | | | | | D04502J | | 15 | | ALL |
| W0511 | 286T0511 | | | RADIO ALTM L,SHELF TO SHELF | | | | | | | | | | | | | |
| 001 | 24 | | PK | 46-0 | 22-12-11 | D04415J | | 6 | | | | | D04417J | | 6 | | ALL |
| 002 | 24 | | PK | 46-0 | 34-33-11 | D04415J | | 5 | | | | | D04417J | | 5 | | ALL |
| 003 | 24 | | PK | 46-0 | 34-33-21 | D04415J | | 4 | | | | | D04417J | | 4 | | ALL |
| 004 | 24 | | PK | 46-0 | 34-33-31 | D04415J | | 10 | | | | | D04417J | | 10 | | ALL |
| 005 | 24 | | PK | 46-0 | 34-57-11 | D04415J | | 11 | | | | | D04417J | | 11 | | ALL |
| 006 | 22 | | PA | 46-0 | SPARE | D04415J | | 12 | | | | | D04417J | | 12 | | ALL |
| 007 | 22 | | PA | 46-0 | SPARE | D04415J | | 13 | | | | | D04417J | | 13 | | ALL |
| 008 | 22 | | PA | 46-0 | SPARE | D04415J | | 14 | | | | | D04417J | | 14 | | ALL |
| 009 | 22 | | PA | 46-0 | SPARE | D04415J | | 15 | | | | | D04417J | | 15 | | ALL |
| 010 | 22 | | PA | 46-0 | SPARE | D04415J | | 22 | | | | | D04517J | | 12 | | 050-099 |
| 011 | 24 | | PK | 46-0 | SPARE | D04415J | | 23 | | | | | D04517J | | 13 | | 050-099 |
| 201B | 24 | | PW IA | 46-0 | 22-12-11 | D04415J | | 8 | | | | | D04417J | | 8 | | ALL |
| 201R | 24 | | PW IA | 0-0 | 22-12-11 | D04415J | | 7 | | | | | D04417J | | 7 | | ALL |
| 201Z | | | IA | 0-0 | 22-12-11 | D04415J | | 9 | | | | | D04417J | | 9 | | ALL |
| 202B | 24 | | PW IB | 46-0 | 34-33-11 | D04415J | | 3 | | | | | D04417J | | 3 | | ALL |
| 202R | 24 | | PW IB | 0-0 | 34-33-11 | D04415J | | 2 | | | | | D04417J | | 2 | | ALL |
| 202Z | | | IB | 0-0 | 34-33-11 | D04415J | | 1 | | | | | D04417J | | 1 | | ALL |
| 203B | 24 | | PW IC | 46-0 | 34-22-18 | D04415J | | 17 | | | | | D04417J | | 17 | | ALL |
| 203R | 24 | | PW IC | 0-0 | 34-22-18 | D04415J | | 16 | | | | | D04417J | | 16 | | ALL |
| 203Z | | | IC | 0-0 | 34-22-18 | D04415J | | 18 | | | | | D04417J | | 18 | | ALL |
| 204B | 24 | | PW ID | 46-0 | 34-22-28 | D04415J | | 20 | | | | | D04517J | | 10 | | 050-099 |
| 204B | 24 | | PW ID | 47-0 | 34-22-28 | D04517J | | 10 | | | | | D04415J | | 20 | | 150-199, 275-299 |
| 204R | 24 | | PW ID | 0-0 | 34-22-28 | D04415J | | 19 | | | | | D04517J | | 9 | | 050-099 |
| 204R | 24 | | PW ID | 0-0 | 34-22-28 | D04517J | | 9 | | | | | D04415J | | 19 | | 150-199, 275-299 |
| 204Z | | | ID | 0-0 | 34-22-28 | D04415J | | 21 | | | | | D04517J | | 11 | | 050-099 |
| 204Z | | | ID | 0-0 | 34-22-28 | D04517J | | 11 | | | | | D04415J | | 21 | | 150-199, 275-299 |
| W0512 | 286T0512 | | | TAIL SEC -L2A- FLT CONT | | | | | | | | | | | | | |
| 001 | 20 | | UA | 22-0 | 27-23-11 | D05942J | | 1 | | | | | D01890 | | 10 | | 050-099 |
| 001 | 20 | | UA | 20-11 | 27-23-11 | D05942J | | 1 | | | | | D01890 | | 10 | | 150-199, 275-299 |
| 002 | 20 | | UA | 22-0 | 27-23-11 | D05942J | | 2 | | | | | D01890 | | 2 | | 050-099 |
| 002 | 20 | | UA | 20-11 | 27-23-11 | D05942J | | 2 | | | | | D01890 | | 2 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0510

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|--|-------|-------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0512 | 286T0512 | TAIL SEC -L2A- FLT CONT (continued) | | | | | | | | | | | | | |
| 003 | 20 | UA | | 22-0 | 27-23-11 | D05942J | | 3 | | | D01890 | | 3 | | 050-099 |
| 003 | 20 | UA | | 20-11 | 27-23-11 | D05942J | | 3 | | | D01890 | | 3 | | 150-199, 275-299 |
| 004 | 18 | UA | | 5-0 | 27-23-11 | GD00798 | | D.. | N | | D01890 | | 1 | | 050-099 |
| 004 | 18 | UA | | 3-1 | 27-23-11 | GD00798 | | D.. | N | | D01890 | | 1 | | 150-199, 275-299 |
| 005 | 18 | UA | | 5-0 | 27-23-11 | GD00798 | | D.. | N | | D01890 | | 9 | | 050-099 |
| 005 | 18 | UA | | 3-1 | 27-23-11 | GD00798 | | D.. | N | | D01890 | | 9 | | 150-199, 275-299 |
| 006 | 18 | UA | | 27-4 | 32-71-11 | D11080 | | 3 | | | D05942J | | 4 | | 150-199, 275-299 |
| 007 | 18 | UA | | 7-8 | 32-71-11 | D11080 | | 1 | | | GD00808 | D.. | N | | 150-199, 275-299 |
| 008 | 18 | UA | | 27-4 | 32-71-11 | D11080 | | 2 | | | D05942J | | 5 | | 150-199, 275-299 |
| W0513 | 286T0513 | RADIO ALTM C,SHELF TO SHELF | | | | | | | | | | | | | |
| 001 | 24 | PK | | 41-0 | 22-12-31 | D04419J | | 6 | | | D04421J | | 6 | | 050-099 |
| 001 | 24 | PK | | 40-0 | 22-12-31 | D04419J | | 6 | | | D04421J | | 6 | | 150-199, 275-299 |
| 002 | 22 | PA | | 41-0 | SPARE | D04419J | | 4 | | | D04421J | | 4 | | 050-099 |
| 002 | 22 | PA | | 40-0 | SPARE | D04419J | | 4 | | | D04421J | | 4 | | 150-199, 275-299 |
| 003 | 22 | PA | | 41-0 | SPARE | D04419J | | 10 | | | D04421J | | 10 | | 050-099 |
| 003 | 22 | PA | | 40-0 | SPARE | D04419J | | 10 | | | D04421J | | 10 | | 150-199, 275-299 |
| 004 | 22 | PA | | 41-0 | SPARE | D04419J | | 11 | | | D04421J | | 11 | | 050-099 |
| 004 | 22 | PA | | 40-0 | SPARE | D04419J | | 11 | | | D04421J | | 11 | | 150-199, 275-299 |
| 005 | 24 | PK | | 41-0 | 34-33-31 | D04419J | | 5 | | | D04421J | | 5 | | 050-099 |
| 005 | 24 | PK | | 40-0 | 34-33-31 | D04419J | | 5 | | | D04421J | | 5 | | 150-199, 275-299 |
| 006 | 22 | PA | | 41-0 | SPARE | D04419J | | 12 | | | D04421J | | 12 | | 050-099 |
| 006 | 22 | PA | | 40-0 | SPARE | D04419J | | 12 | | | D04421J | | 12 | | 150-199, 275-299 |
| 201B | 24 | PW | IA | 41-0 | 22-12-31 | D04419J | | 8 | | | D04421J | | 8 | | 050-099 |
| 201B | 24 | PW | IA | 40-0 | 22-12-31 | D04419J | | 8 | | | D04421J | | 8 | | 150-199, 275-299 |
| 201R | 24 | PW | IA | 0-0 | 22-12-31 | D04419J | | 7 | | | D04421J | | 7 | | ALL |
| 201Z | | | IA | 0-0 | 22-12-31 | D04419J | | 9 | | | D04421J | | 9 | | ALL |
| 202B | 24 | PW | IB | 41-0 | 34-22-39 | D04419J | | 3 | | | D04421J | | 3 | | 050-099 |
| 202B | 24 | PW | IB | 40-0 | 34-22-39 | D04419J | | 3 | | | D04421J | | 3 | | 150-199, 275-299 |
| 202R | 24 | PW | IB | 0-0 | 34-22-39 | D04419J | | 2 | | | D04421J | | 2 | | ALL |
| 202Z | | | IB | 0-0 | 34-22-39 | D04419J | | 1 | | | D04421J | | 1 | | ALL |
| W0514 | 286T0514 | L & R INBD ELEV POS XMTR STAB | | | | | | | | | | | | | |
| 001 | 20 | UA | | 19-10 | 27-38-11 | D01858 | | 2 | | | SP01742 | | 9 | | ALL |
| 002 | 20 | UA | | 22-4 | 27-38-11 | D01858 | | 5 | | | SP02656 | | 9 | | ALL |
| 003 | 20 | UA | | 22-4 | 27-38-11 | D01858 | | 4 | | | SP02660 | | 9 | | ALL |
| 004 | 18 | UA | | 2-0 | 27-38-11 | D01858 | | 1 | DK | | GD00806 | A.. | N | | ALL |
| 006 | 20 | UA | | 21-3 | 27-38-11 | D01860 | | 3 | | | SP05090 | | 9 | | 155, 157, 167-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0510
Page 8
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0514 | 286T0514 | | | L & R INBD ELEV POS XMTR STAB (continued) | | | | | | | | | | | | | |
| 007 | 20 | | UA | 19-10 | 27-38-11 | D01858 | | 3 | | | | | SP05092 | | 9 | | 155, 157, 167-199, 277-299 |
| 011 | 20 | | UA | 21-3 | 27-38-11 | D01860 | | 2 | | | | | SP01728 | | 9 | | ALL |
| 012 | 20 | | UA | 23-9 | 27-38-11 | D01860 | | 5 | | | | | SP02648 | | 9 | | ALL |
| 013 | 20 | | UA | 23-9 | 27-38-11 | D01860 | | 4 | | | | | SP02652 | | 9 | | ALL |
| 014 | 18 | | UA | 2-0 | 27-38-11 | D01860 | | 1 | DK | | | | GD00810 | A.. | N | | ALL |
| A-A | | | | 0-0 | 27-38-11 | M01145 | | A | | | | | SP02648 | | 9 | | ALL |
| A-B | | | | 0-0 | 27-38-11 | M01144 | | A | | | | | SP02652 | | 9 | | ALL |
| A-C | | | | 0-0 | 27-38-11 | M01147 | | A | | | | | SP02656 | | 9 | | ALL |
| A-D | | | | 0-0 | 27-38-11 | M01146 | | A | | | | | SP02660 | | 9 | | ALL |
| W0515 | 286T0515 | | | RADIO ALTM R,SHELF TO SHELF | | | | | | | | | | | | | |
| 001 | 24 | | PK | 35-0 | 22-12-21 | D04423J | | 6 | | | | | D05575J | | 6 | | ALL |
| 004 | 24 | | PK | 35-0 | 34-33-21 | D04423J | | 4 | | | | | D05575J | | 4 | | ALL |
| 005 | 24 | | PK | 35-0 | SPARE | D04423J | | 5 | | | | | D05575J | | 5 | | ALL |
| 010 | 24 | | PK | 35-0 | SPARE | D04423J | | 10 | | | | | D05575J | | 10 | | ALL |
| 201B | 24 | | PW IA | 35-0 | 22-12-21 | D04423J | | 8 | | | | | D05575J | | 8 | | ALL |
| 201R | 24 | | PW IA | 0-0 | 22-12-21 | D04423J | | 7 | | | | | D05575J | | 7 | | ALL |
| 201Z | | | IA | 0-0 | 22-12-21 | D04423J | | 9 | | | | | D05575J | | 9 | | ALL |
| 202B | 24 | | PW IB | 35-0 | 34-33-21 | D04423J | | 3 | | | | | D05575J | | 3 | | ALL |
| 202R | 24 | | PW IB | 0-0 | 34-33-21 | D04423J | | 2 | | | | | D05575J | | 2 | | ALL |
| 202Z | | | IB | 0-0 | 34-33-21 | D04423J | | 1 | | | | | D05575J | | 1 | | ALL |
| 203B | 24 | | PW IC | 35-0 | 34-22-28 | D04423J | | 20 | | | | | D05575J | | 20 | | 050-099 |
| 203B | 24 | | PW IC | 35-0 | 34-22-28 | D05575J | | 20 | | | | | D04423J | | 20 | | 150-199, 275-299 |
| 203R | 24 | | PW IC | 0-0 | 34-22-28 | D04423J | | 19 | | | | | D05575J | | 19 | | 050-099 |
| 203R | 24 | | PW IC | 0-0 | 34-22-28 | D05575J | | 19 | | | | | D04423J | | 19 | | 150-199, 275-299 |
| 203Z | | | IC | 0-0 | 34-22-28 | D04423J | | 21 | | | | | D05575J | | 21 | | 050-099 |
| 203Z | | | IC | 0-0 | 34-22-28 | D05575J | | 21 | | | | | D04423J | | 21 | | 150-199, 275-299 |
| 204B | 24 | | PW ID | 40-0 | 34-22-18 | D04423J | | 17 | | | | | D04545J | | 7 | | 050-099 |
| 204B | 24 | | PW 1D | 40-0 | 34-22-18 | D04423J | | 17 | | | | | D04545J | | 7 | | 150-199, 275-299 |
| 204R | 24 | | PW ID | 0-0 | 34-22-18 | D04423J | | 16 | | | | | D04545J | | 6 | | 050-099 |
| 204R | 24 | | PW 1D | 0-0 | 34-22-18 | D04423J | | 16 | | | | | D04545J | | 6 | | 150-199, 275-299 |
| 204Z | | | ID | 0-0 | 34-22-18 | D04423J | | 18 | | | | | D04545J | | 8 | | 050-099 |
| 204Z | | | 1D | 0-0 | 34-22-18 | D04423J | | 18 | | | | | D04545J | | 8 | | 150-199, 275-299 |
| 205B | 24 | | PW IE | 35-0 | 31-35-13 | D04423J | | 12 | | | | | D05575J | | 12 | | ALL |
| 205R | 24 | | PW IE | 0-0 | 31-35-13 | D04423J | | 11 | | | | | D05575J | | 11 | | ALL |
| 205Z | | | IE | 0-0 | 31-35-13 | D04423J | | 13 | | | | | D05575J | | 13 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0510

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0516 | 286T0516 | | | L WING INBD FS-L2B - EEC | | | | | | | | | | | | |
| 001 | 18 | UA | | | 23-3 | 30-34-11 | D06384J | | 1 | | | D06578P | 14 | DL | | ALL |
| 002 | 16 | VF | AB | | 23-3 | 73-21-20 | D06384J | | 13 | | | D06578P | 13 | FL | | ALL |
| 002Z | | | AB | | 0-0 | 73-21-20 | D06384J | =CC | M | | | D06578P | =CC | M | | ALL |
| 101 | 20 | VF | EA | | 23-3 | 73-21-14 | D06384J | | 11 | | | D06578P | 2 | | | ALL |
| 101Z | | | EA | | 0-0 | 73-21-14 | D06384J | =CC | M | | | D06578P | =CC | M | | ALL |
| 201B | 20 | VG | IA | | 23-3 | 73-21-13 | D06384J | | 15 | | | D06578P | 15 | | | ALL |
| 201R | 20 | VG | IA | | 0-0 | 73-21-13 | D06384J | | 16 | | | D06578P | 16 | | | ALL |
| 201Z | | | IA | | 0-0 | 73-21-13 | D06384J | =CC | M | | | D06578P | =CC | M | | ALL |
| 202B | 20 | VG | IB | | 23-3 | 73-21-14 | D06384J | | 6 | | | D06578P | 17 | | | ALL |
| 202R | 20 | VG | IB | | 0-0 | 73-21-14 | D06384J | | 5 | | | D06578P | 18 | | | ALL |
| 202Z | | | IB | | 0-0 | 73-21-14 | D06384J | =CC | M | | | D06578P | =CC | M | | ALL |
| 203B | 20 | VG | IC | | 23-3 | 31-35-14 | D06384J | | 21 | | | D06578P | 6 | | | 050-099 |
| 203B | 20 | VG | IC | | 23-3 | 31-35-14 | D06578P | | 6 | | | D06384J | 21 | | | 150-199, 275-276, 278-299 |
| 203R | 20 | VG | IC | | 0-0 | 31-35-14 | D06384J | | 20 | | | D06578P | 5 | | | 050-099 |
| 203R | 20 | VG | IC | | 0-0 | 31-35-14 | D06578P | | 5 | | | D06384J | 20 | | | 150-199, 275-276, 278-299 |
| 203Z | | | IC | | 0-0 | 31-35-14 | D06384J | =CC | M | | | D06578P | =CC | M | | 050-099 |
| 203Z | | | IC | | 0-0 | 31-35-14 | D06578P | =CC | M | | | D06384J | =CC | M | | 150-199, 275-276, 278-299 |
| 204B | 20 | VG | ID | | 23-3 | 73-21-14 | D06384J | | 24 | | | D06578P | 21 | | | ALL |
| 204R | 20 | VG | ID | | 0-0 | 73-21-14 | D06384J | | 23 | | | D06578P | 22 | | | ALL |
| 204Z | | | ID | | 0-0 | 73-21-14 | D06384J | =CC | M | | | D06578P | =CC | M | | ALL |
| 205B | 20 | VG | IE | | 23-3 | 77-12-11 | D06578P | | 3 | | | D06384J | 3 | | | ALL |
| 205R | 20 | VG | IE | | 0-0 | 77-12-11 | D06578P | | 4 | | | D06384J | 2 | | | ALL |
| 205Z | | | IE | | 0-0 | 77-12-11 | D06578P | =CC | M | | | D06384J | =CC | M | | ALL |
| 211B | 20 | VG | IK | | 23-3 | 73-21-17 | D06384J | | 28 | | | D06578P | 10 | | | ALL |
| 211R | 20 | VG | IK | | 0-0 | 73-21-12 | D06384J | | 17 | | | D06578P | 1 | | | ALL |
| 211Z | | | IK | | 0-0 | 73-21-12 | D06384J | =CC | M | | | D06578P | =CC | M | | ALL |
| 223B | 20 | VG | IW | | 23-3 | 73-21-14 | D06384J | | 8 | | | D06578P | 12 | | | ALL |
| 223R | 20 | VG | IW | | 0-0 | 73-21-14 | D06384J | | 7 | | | D06578P | 11 | | | ALL |
| 223Z | | | IW | | 0-0 | 73-21-14 | D06384J | =CC | M | | | D06578P | =CC | M | | ALL |
| 225B | 20 | HQ | IY | | 23-3 | 73-21-11 | D06578P | | 8 | | | D06384J | 10 | | | ALL |
| 225R | 20 | HQ | IY | | 0-0 | 73-21-11 | D06578P | | 9 | | | D06384J | 19 | | | ALL |
| 225Z | | | IY | | 0-0 | 73-21-11 | D06578P | =CC | M | | | D06384J | =CC | M | | ALL |
| 302B | 20 | VH | MB | | 23-3 | 73-21-13 | D06384J | | 27 | | | D06578P | 27 | | | ALL |
| 302R | 20 | VH | MB | | 0-0 | 73-21-13 | D06384J | | 26 | | | D06578P | 26 | | | ALL |
| 302Y | 20 | VH | MB | | 0-0 | 73-21-13 | D06384J | | 25 | | | D06578P | 25 | | | ALL |
| 302Z | | | MB | | 0-0 | 73-21-13 | D06384J | =CC | M | | | D06578P | =CC | M | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0510
 Page 10
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|------|------|--------|-------------|------|-----|---|---------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0517 | 286T0517 | | | FMC L,SHELVES TO CONT DISPLAY UNIT | | | | | | | | | | | | | | | | |
| 001 | 24 | | PK | | 17-0 | 34-61-16 | D02287 | | 23 | | | | | | | TB0255X | C001 | BJ | | ALL |
| 002 | 22 | | PA | | 27-0 | 31-31-26 | TB0255X | | A001 | BJ | | | | | | D05427J | 7 | | | ALL |
| 010 | 24 | | PK | | 37-0 | 34-61-11 | D04429J | | 10 | | | | | | | D00465 | 29 | | | ALL |
| 012 | 20 | | PA | | 3-0 | 34-61-11 | GD00207 | | D.. | 2 | | | | | | D00465 | 30 | | | ALL |
| 023 | 22 | | PA | | 17-0 | 33-16-18 | TB0031Y | | C004 | BJ | | | | | | D00465 | 33 | | | ALL |
| 025 | 20 | | PA | | 3-0 | 34-61-11 | GD00207 | | S.. | 2 | | | | | | D00465 | 34 | | | ALL |
| 026 | 20 | | PA | | 3-0 | 34-61-11 | GD00207 | | D.. | 2 | | | | | | D00465 | 36 | | | ALL |
| 027 | 22 | | PA | | 17-0 | 33-16-18 | TB0031Y | | A004 | BJ | | | | | | D00465 | 35 | | | ALL |
| 028 | 18 | | PA | | 14-0 | 33-13-18 | SP02290 | | | 9 | | | | | | D00465 | 37 | DK | | ALL |
| 029 | 18 | | PA | | 2-0 | 33-13-18 | GD00207 | | A.. | 2 | | | | | | D00465 | 38 | DK | | ALL |
| 030 | 24 | | PK | | 37-0 | 34-61-11 | D04429J | | | 7 | | | | | | D00465 | 40 | | | 050-099, 275-299 |
| 030 | 24 | | PK | | 38-0 | 34-61-11 | D04429J | | | 7 | | | | | | D00465 | 40 | | | 150-199 |
| 031 | 20 | | PA | | 3-0 | 34-61-11 | GD00207 | | A.. | 2 | | | | | | D00465 | 41 | | | 050-099, 150-155, 162-165, 275-299 |
| 031 | 20 | | PA | | 4-0 | 34-61-11 | GD00208 | | A.. | 2 | | | | | | D00465 | 41 | | | 156-157, 166-199 |
| 101 | 24 | | PK | | 38-0 | 34-61-16 | D05427J | | | 8 | | | | | | SM00001 | | 9 | | ALL |
| 102 | 24 | | PK | | 1-0 | 34-61-16 | D02287 | | | 32 | | | | | | SM00001 | | 9 | | ALL |
| 103 | 24 | | PK | | 3-0 | 34-61-16 | D02287 | | | 33 | | | | | | SM00001 | | 9 | | 050-099 |
| 103 | 24 | | PK | | 1-0 | 34-61-16 | D02287 | | | 33 | | | | | | SM00001 | | 9 | | 150-199, 275-299 |
| 201B | 24 | | PW | IA | 37-0 | 34-61-11 | D04429J | | | 3 | | | | | | D00465 | | 3 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-61-11 | D04429J | | | 2 | | | | | | D00465 | | 2 | | ALL |
| 201Z | | | | IA | 0-0 | 34-61-11 | D04429J | | | 1 | | | | | | GD00207 | | S.. | 2 | ALL |
| 202B | 24 | | PW | IB | 39-0 | 34-61-11 | D05427J | | | 6 | | | | | | D00465 | | 6 | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-61-11 | D05427J | | | 5 | | | | | | D00465 | | 5 | | ALL |
| 202Z | | | | IB | 0-0 | 34-61-11 | D05427J | | | 4 | | | | | | GD00207 | | S.. | 2 | ALL |
| 203B | 24 | | PW | IC | 37-0 | 34-61-11 | D04429J | | | 9 | | | | | | D00465 | | 28 | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 34-61-11 | D04429J | | | 8 | | | | | | D00465 | | 27 | | ALL |
| 203Z | | | | IC | 0-0 | 34-61-11 | D04429J | | | 4 | | | | | | GD00207 | | S.. | 2 | ALL |
| 204B | 24 | | PW | ID | 37-0 | 31-35-11 | D00465 | | | 25 | | | | | | D04429J | | 12 | | ALL |
| 204R | 24 | | PW | ID | 0-0 | 31-35-11 | D00465 | | | 24 | | | | | | D04429J | | 11 | | ALL |
| 204Z | | | | ID | 0-0 | 31-35-11 | GD00207 | | S.. | 2 | | | | | | D04429J | | 13 | | ALL |
| 205B | 24 | | PW | IE | 17-0 | 23-22-11 | D00465 | | | 9 | | | | | | TB0255Y | C003 | BJ | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 23-22-11 | D00465 | | | 8 | | | | | | TB0255Y | A003 | BJ | | ALL |
| 205Z | | | | IE | 0-0 | 23-22-11 | GD00207 | | S.. | 2 | | | | | | TB0255Y | A004 | BJ | | ALL |
| 206B | 24 | | PW | IF | 26-0 | 34-61-16 | D04429J | | | 21 | | | | | | TB0255X | C005 | BJ | | ALL |
| 206R | 24 | | PW | IF | 0-0 | 34-61-16 | D04429J | | | 20 | | | | | | TB0255X | B005 | BJ | | ALL |
| 206Z | | | | IF | 0-0 | 34-61-16 | D04429J | | | 22 | | | | | | TB0255X | A005 | BJ | | ALL |
| 207 | 20 | | UA | | 1-6 | 34-61-16 | D02287 | | REF | | | IG | | | | GD00208 | | S.. | 2 | 156, 166 |
| 207B | 24 | | PW | IG | 37-0 | 34-61-16 | D02287 | | | 9 | | | | | | D04429J | | 18 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0510

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|----------|---------|---------|-------|------|------|---------|-------|------|------|---|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0517 | 286T0517 | | | FMC L,SHELVES TO CONT DISPLAY UNIT (continued) | | | | | | | | | | | |
| 207R | 24 | PW | IG | 0-0 | 34-61-16 | D02287 | | 8 | | | D04429J | 17 | | | ALL |
| 207Z | | | IG | 0-0 | 34-61-16 | GD00207 | | S.. | 2 | | D04429J | 19 | | | 050-099, 275-276 |
| 207Z | | | IG | 0-0 | 34-61-16 | GD00235 | | S.. | 2 | | D04429J | 19 | | | 150-154 |
| 207Z | | | IG | 0-0 | 34-61-16 | GD00208 | | S.. | 2 | | D04429J | 19 | | | 155, 157-165, 167-199, 277-299 |
| 207Z | | | IG | 0-0 | 34-61-16 | D02287 | | REF | | IG | D04429J | 19 | | | 156, 166 |
| 208 | 20 | UA | | 1-6 | 34-61-16 | D02287 | | REF | | IH | GD00208 | S.. | 2 | | 156, 166 |
| 208B | 24 | PW | IH | 38-0 | 34-61-16 | D02287 | | 3 | | | D04429J | 15 | | | ALL |
| 208R | 24 | PW | IH | 0-0 | 34-61-16 | D02287 | | 2 | | | D04429J | 14 | | | ALL |
| 208Z | | | IH | 0-0 | 34-61-16 | GD00208 | | S.. | 2 | | D04429J | 16 | | | 050-099, 155, 157-165, 167-199, 275-299 |
| 208Z | | | IH | 0-0 | 34-61-16 | GD00235 | | S.. | 2 | | D04429J | 16 | | | 150-154 |
| 208Z | | | IH | 0-0 | 34-61-16 | D02287 | | REF | | IH | D04429J | 16 | | | 156, 166 |
| 209 | 20 | UA | | 1-6 | 34-61-16 | D02287 | | REF | | II | GD00208 | S.. | 2 | | 156, 166 |
| 209B | 24 | PW | II | 38-0 | 34-61-16 | D02287 | | 6 | | | D05427J | 2 | | | ALL |
| 209R | 24 | PW | II | 0-0 | 34-61-16 | D02287 | | 5 | | | D05427J | 1 | | | ALL |
| 209Z | | | II | 0-0 | 34-61-16 | GD00208 | | S.. | 2 | | D05427J | 3 | | | 050-099, 155, 157-165, 167-199, 275-299 |
| 209Z | | | II | 0-0 | 34-61-16 | GD00235 | | S.. | 2 | | D05427J | 3 | | | 150-154 |
| 209Z | | | II | 0-0 | 34-61-16 | D02287 | | REF | | II | D05427J | 3 | | | 156, 166 |
| 210B | 24 | PW | IJ | 37-0 | 23-25-13 | D04429J | | 24 | | | D00465 | 12 | | | 156-157, 166-199, 277-299 |
| 210R | 24 | PW | IJ | 0-0 | 23-25-13 | D04429J | | 23 | | | D00465 | 11 | | | 156-157, 166-199, 277-299 |
| 210Z | | | IJ | 0-0 | 23-25-13 | D04429J | | 5 | | | GD00208 | S.. | 2 | | 156-157, 166-199, 277-299 |
| W0518 | 286T0518 | | | R WING INBD FS-R2B- EEC | | | | | | | | | | | |
| 001 | 18 | UA | | 23-7 | 30-34-21 | D06382J | | 1 | | | D06580P | 14 | DL | | ALL |
| 002 | 16 | VF | EB | 23-7 | 73-21-20 | D06382J | | 13 | | | D06580P | 13 | FL | | ALL |
| 002Z | | | EB | 0-0 | 73-21-20 | D06382J | | =CC | M | | D06580P | =CC | M | | ALL |
| 101 | 20 | VF | EA | 23-7 | 73-21-14 | D06382J | | 11 | | | D06580P | 2 | | | ALL |
| 101Z | | | EA | 0-0 | 73-21-14 | D06382J | | =CC | M | | D06580P | =CC | M | | ALL |
| 201B | 20 | VG | IA | 23-7 | 73-21-13 | D06382J | | 15 | | | D06580P | 15 | | | ALL |
| 201R | 20 | VG | IA | 0-0 | 73-21-13 | D06382J | | 16 | | | D06580P | 16 | | | ALL |
| 201Z | | | IA | 0-0 | 73-21-13 | D06382J | | =CC | M | | D06580P | =CC | M | | ALL |
| 202B | 20 | VG | IB | 23-7 | 73-21-14 | D06382J | | 6 | | | D06580P | 17 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0510
Page 12
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0518 | 286T0518 | | | R WING INBD FS-R2B- EEC (continued) | | | | | | | | | | | | | |
| 202R | 20 | VG | IB | 0-0 | 73-21-14 | D06382J | | 5 | | | | | D06580P | 18 | | | ALL |
| 202Z | | | IB | 0-0 | 73-21-14 | D06382J | =CC | M | | | | | D06580P | =CC | M | | ALL |
| 203B | 20 | VG | IC | 23-7 | 31-35-15 | D06382J | | 21 | | | | | D06580P | 6 | | | 050-099 |
| 203B | 20 | VG | IC | 23-7 | 31-35-15 | D06580P | | 6 | | | | | D06382J | 21 | | | 150-199, 275-276, 278-299 |
| 203R | 20 | VG | IC | 0-0 | 31-35-15 | D06382J | | 20 | | | | | D06580P | 5 | | | 050-099 |
| 203R | 20 | VG | IC | 0-0 | 31-35-15 | D06580P | | 5 | | | | | D06382J | 20 | | | 150-199, 275-276, 278-299 |
| 203Z | | | IC | 0-0 | 31-35-15 | D06382J | =CC | M | | | | | D06580P | =CC | M | | 050-099 |
| 203Z | | | IC | 0-0 | 31-35-15 | D06580P | =CC | M | | | | | D06382J | =CC | M | | 150-199, 275-276, 278-299 |
| 204B | 20 | VG | ID | 23-7 | 73-21-14 | D06382J | | 24 | | | | | D06580P | 21 | | | ALL |
| 204R | 20 | VG | ID | 0-0 | 73-21-14 | D06382J | | 23 | | | | | D06580P | 22 | | | ALL |
| 204Z | | | ID | 0-0 | 73-21-14 | D06382J | =CC | M | | | | | D06580P | =CC | M | | ALL |
| 205B | 20 | VG | IE | 23-7 | 77-12-11 | D06580P | | 3 | | | | | D06382J | 3 | | | ALL |
| 205R | 20 | VG | IE | 0-0 | 77-12-11 | D06580P | | 4 | | | | | D06382J | 2 | | | ALL |
| 205Z | | | IE | 0-0 | 77-12-11 | D06580P | =CC | M | | | | | D06382J | =CC | M | | ALL |
| 211B | 20 | VG | IK | 23-7 | 73-21-17 | D06580P | | 10 | | | | | D06382J | 28 | | | ALL |
| 211R | 20 | VG | IK | 0-0 | 73-21-12 | D06382J | | 17 | | | | | D06580P | 1 | | | 050-099, 275-299 |
| 211R | 20 | VG | IK | 0-0 | 73-21-12 | D06580P | | 1 | | | | | D06382J | 17 | | | 150-199 |
| 211Z | | | IK | 0-0 | 73-21-12 | D06580P | =CC | M | | | | | D06382J | =CC | M | | ALL |
| 223B | 20 | VG | IT | 23-7 | 73-21-14 | D06382J | | 8 | | | | | D06580P | 12 | | | ALL |
| 223R | 20 | VG | IT | 0-0 | 73-21-14 | D06382J | | 7 | | | | | D06580P | 11 | | | ALL |
| 223Z | | | IT | 0-0 | 73-21-14 | D06382J | =CC | M | | | | | D06580P | =CC | M | | ALL |
| 225B | 20 | HQ | IY | 23-7 | 73-21-11 | D06580P | | 8 | | | | | D06382J | 10 | | | ALL |
| 225R | 20 | HQ | IY | 0-0 | 73-21-11 | D06580P | | 9 | | | | | D06382J | 19 | | | ALL |
| 225Z | | | IY | 0-0 | 73-21-11 | D06580P | =CC | M | | | | | D06382J | =CC | M | | ALL |
| 302B | 20 | VH | C | 23-7 | 73-21-13 | D06382J | | 27 | | | | | D06580P | 27 | | | ALL |
| 302R | 20 | VH | C | 0-0 | 73-21-13 | D06382J | | 26 | | | | | D06580P | 26 | | | ALL |
| 302Y | 20 | VH | C | 0-0 | 73-21-13 | D06382J | | 25 | | | | | D06580P | 25 | | | ALL |
| 302Z | | | C | 0-0 | 73-21-13 | D06382J | =CC | M | | | | | D06580P | =CC | M | | ALL |
| W0519 | 286T0519 | | | FMC R,SHELVES TO CONT DISPLAY UNIT | | | | | | | | | | | | | |
| 001 | 24 | PK | | 17-0 | 34-61-26 | D02289 | | 23 | | | | | TB0255X | D001 | BJ | | ALL |
| 010 | 24 | PK | | 43-0 | 34-61-21 | D04433J | | 10 | | | | | D00467 | 29 | | | ALL |
| 012 | 20 | PA | | 3-0 | 34-61-21 | GD00235 | | D.. | 2 | | | | D00467 | 31 | | | ALL |
| 023 | 22 | PA | | 29-0 | 33-16-18 | SP00273 | | | S | | | | D00467 | 33 | | | ALL |
| 025 | 20 | PA | | 3-0 | 34-61-21 | GD00235 | | S.. | 2 | | | | D00467 | 34 | | | ALL |
| 026 | 20 | PA | | 3-0 | 34-61-21 | GD00235 | | D.. | 2 | | | | D00467 | 36 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0510

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0519 | 286T0519 | | | FMC R,SHELVES TO CONT DISPLAY UNIT (continued) | | | | | | | | | | | | | | |
| 027 | 22 | | PA | | 29-0 | 33-16-18 | SP00271 | | | S | | | | D00467 | 35 | | | ALL |
| 028 | 18 | | PA | | 14-0 | 33-13-18 | SP02284 | | | 9 | | | | D00467 | 37 | DK | | ALL |
| 029 | 18 | | PA | | 3-0 | 33-13-18 | GD00235 | | | A.. | 2 | | | D00467 | 38 | DK | | ALL |
| 030 | 24 | | PK | | 43-0 | 34-61-21 | D04433J | | | 7 | | | | D00467 | 40 | | | ALL |
| 031 | 20 | | PA | | 3-0 | 34-61-21 | GD00235 | | | A.. | 2 | | | D00467 | 41 | | | 050-099, 150-155, 162-165, 275-299 |
| 031 | 20 | | PA | | 4-0 | 34-61-21 | GD00765 | | | A.. | 2 | | | D00467 | 41 | | | 156-157, 166-199 |
| 101 | 24 | | PK | | 43-0 | 34-61-26 | D04433J | | | 8 | | | | SM00001 | | 9 | | ALL |
| 102 | 24 | | PK | | 3-0 | 34-61-26 | D02289 | | | 32 | | | | SM00001 | | 9 | | ALL |
| 103 | 24 | | PK | | 3-0 | 34-61-26 | D02289 | | | 33 | | | | SM00001 | | 9 | | ALL |
| 201B | 24 | | PW | IA | 43-0 | 34-61-21 | D04433J | | | 3 | | | | D00467 | 3 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-61-21 | D04433J | | | 2 | | | | D00467 | 2 | | | ALL |
| 201Z | | | | IA | 0-0 | 34-61-21 | D04433J | | | 1 | | | | GD00235 | S.. | 2 | | ALL |
| 202B | 24 | | PW | IB | 42-0 | 34-61-11 | D05425J | | | 6 | | | | D00467 | 6 | | | 050-099, 275-299 |
| 202B | 24 | | PW | IB | 43-0 | 34-61-11 | D05425J | | | 6 | | | | D00467 | 6 | | | 150-199 |
| 202R | 24 | | PW | IB | 0-0 | 34-61-11 | D05425J | | | 5 | | | | D00467 | 5 | | | ALL |
| 202Z | | | | IB | 0-0 | 34-61-11 | D05425J | | | 4 | | | | GD00235 | S.. | 2 | | ALL |
| 203B | 24 | | PW | IC | 43-0 | 34-61-21 | D04433J | | | 5 | | | | D00467 | 28 | | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 34-61-21 | D04433J | | | 4 | | | | D00467 | 27 | | | ALL |
| 203Z | | | | IC | 0-0 | 34-61-21 | D04433J | | | 6 | | | | GD00235 | S.. | 2 | | ALL |
| 204B | 24 | | PW | ID | 43-0 | 31-35-11 | D00467 | | | 25 | | | | D05425J | 2 | | | ALL |
| 204R | 24 | | PW | ID | 0-0 | 31-35-11 | D00467 | | | 24 | | | | D05425J | 1 | | | ALL |
| 204Z | | | | ID | 0-0 | 31-35-11 | GD00235 | | | S.. | 2 | | | D05425J | 3 | | | ALL |
| 205B | 24 | | PW | IE | 43-0 | 23-22-11 | D00467 | | | 9 | | | | D04433J | 20 | | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 23-22-11 | D00467 | | | 8 | | | | D04433J | 19 | | | ALL |
| 205Z | | | | IE | 0-0 | 23-22-11 | GD00235 | | | S.. | 2 | | | D04433J | 21 | | | ALL |
| 206B | 24 | | PW | IF | 49-2 | 34-61-26 | D04433J | | | 23 | | | | TB0255X | B006 | BJ | | 050-099, 150-155, 162-165, 275-299 |
| 206B | 24 | | PW | IF | 50-2 | 34-61-26 | D04433J | | | 23 | | | | TB0255X | B006 | BJ | | 156-157, 166-199 |
| 206R | 24 | | PW | IF | 0-0 | 34-61-26 | D04433J | | | 22 | | | | TB0255X | A006 | BJ | | ALL |
| 206Z | | | | IF | 0-0 | 34-61-26 | D04433J | | | 24 | | | | TB0255X | D005 | BJ | | ALL |
| 207 | 20 | | UA | | 1-6 | 34-61-26 | D02289 | | | REF | | IG | | GD00765 | S.. | 2 | | 156, 166 |
| 207B | 24 | | PW | IG | 43-0 | 34-61-26 | D02289 | | | 3 | | | | D04433J | 14 | | | ALL |
| 207R | 24 | | PW | IG | 0-0 | 34-61-26 | D02289 | | | 2 | | | | D04433J | 13 | | | ALL |
| 207Z | | | | IG | 0-0 | 34-61-26 | GD00235 | | | S.. | 2 | | | D04433J | 15 | | | 050-099, 150-155, 162-165, 275-299 |
| 207Z | | | | IG | 0-0 | 34-61-26 | D02289 | | | REF | | IG | | D04433J | 15 | | | 156, 166 |
| 207Z | | | | IG | 0-0 | 34-61-26 | GD00765 | | | S.. | 2 | | | D04433J | 15 | | | 157, 167-199 |
| 208 | 20 | | UA | | 1-6 | 34-61-26 | D02289 | | | REF | | IH | | GD00235 | S.. | 2 | | 150-151 |

WIRE LIST
D280T132

91-21-11
Section W0510
Page 14
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0519 | 286T0519 | | | FMC R,SHELVES TO CONT DISPLAY UNIT (continued) | | | | | | | | | | | |
| 208 | 20 | UA | | 1-6 | 34-61-26 | D02289 | REF | | IH | GD00765 | S.. | 2 | | 156, 166 | |
| 208B | 24 | PW | IH | 43-0 | 34-61-26 | D02289 | 9 | | | D04433J | 17 | | | ALL | |
| 208R | 24 | PW | IH | 0-0 | 34-61-26 | D02289 | 8 | | | D04433J | 16 | | | ALL | |
| 208Z | | | IH | 0-0 | 34-61-26 | GD00235 | S.. | 2 | | D04433J | 18 | | | 050-099, 152-155, 162-165, 275-299 | |
| 208Z | | | IH | 0-0 | 34-61-26 | D02289 | REF | | IH | D04433J | 18 | | | 150-151, 156, 166 | |
| 208Z | | | IH | 0-0 | 34-61-26 | GD00765 | S.. | 2 | | D04433J | 18 | | | 157, 167-199 | |
| 209 | 20 | UA | | 1-6 | 34-61-26 | D02289 | REF | | II | GD00765 | S.. | 2 | | 156, 166 | |
| 209B | 24 | PW | II | 43-0 | 34-61-26 | D02289 | 6 | | | D05425J | 8 | | | ALL | |
| 209R | 24 | PW | II | 0-0 | 34-61-26 | D02289 | 5 | | | D05425J | 7 | | | ALL | |
| 209Z | | | II | 0-0 | 34-61-26 | GD00235 | S.. | 2 | | D05425J | 9 | | | 050-099, 150-155, 162-165, 275-299 | |
| 209Z | | | II | 0-0 | 34-61-26 | D02289 | REF | | II | D05425J | 9 | | | 156, 166 | |
| 209Z | | | II | 0-0 | 34-61-26 | GD00765 | S.. | 2 | | D05425J | 9 | | | 157, 167-199 | |
| 210B | 24 | PW | IJ | 43-0 | 23-25-13 | D04433J | 11 | | | D00467 | 12 | | | 156-157, 166-199, 277-299 | |
| 210R | 24 | PW | IJ | 0-0 | 23-25-13 | D04433J | 9 | | | D00467 | 11 | | | 156-157, 166-199, 277-299 | |
| 210Z | | | IJ | 0-0 | 23-25-13 | D04433J | 12 | | | GD00235 | S.. | 2 | | 156-157, 166-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W0510
Page 15 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|----------|---------|---------|-------|------|------|---------|-------|------|------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0521 | 286T0521 | | | RT. STAB TRIM - BRKT. AC1402 TO CONTROL STAND P10 | | | | | | | | | | | |
| 001 | 20 | PA | | 35-10 | 27-41-31 | D02265J | | 10 | | | SP00427 | | 9 | | 050-099 |
| 001 | 20 | PA | | 36-3 | 27-41-31 | D02265J | | 10 | | | SP00427 | | 9 | | 155-199, 275-299 |
| 002 | 20 | PA | | 35-10 | 27-41-31 | D02265J | | 2 | | | SP00427 | | 9 | | 050-099 |
| 002 | 20 | PA | | 36-3 | 27-41-31 | D02265J | | 2 | | | SP00427 | | 9 | | 155-199, 275-299 |
| 003 | 20 | PA | | 35-10 | 27-41-31 | D02265J | | 8 | | | SP00425 | | 9 | | 050-099 |
| 003 | 20 | PA | | 36-3 | 27-41-31 | D02265J | | 8 | | | SP00425 | | 9 | | 155-199, 275-299 |
| 004Y | 20 | PJ | | 120-2 | 27-41-31 | D02265J | | 11 | | | D06023P | | 1 | | 050-099 |
| 004Y | 20 | PJ | | 141-7 | 27-41-31 | D02265J | | 11 | | | D06023P | | 1 | | 155-199, 275-299 |
| 005Y | 20 | PJ | | 120-2 | 27-41-31 | D02265J | | 12 | | | D06023P | | 2 | | 050-099 |
| 005Y | 20 | PJ | | 141-7 | 27-41-31 | D02265J | | 12 | | | D06023P | | 2 | | 155-199, 275-299 |
| 006Y | 20 | P5 | AF | 120-2 | 27-41-31 | D02265J | | 6 | | | D06025P | | 1 | | 050-099 |
| 006Y | 20 | P5 | AF | 141-7 | 27-41-31 | D02265J | | 6 | | | D06025P | | 1 | | 155-199, 275-299 |
| 006Z | | | AF | 0-0 | 27-41-31 | D02265J | | DED | | | D06025P | | DED | | 050-099, 155-199, 275-299 |
| 007Y | 20 | P5 | AG | 120-2 | 27-41-31 | D02265J | | 5 | | | D06025P | | 2 | | 050-099 |
| 007Y | 20 | P5 | AG | 141-7 | 27-41-31 | D02265J | | 5 | | | D06025P | | 2 | | 155-199, 275-299 |
| 007Z | | | AG | 0-0 | 27-41-31 | D02265J | | DED | | | D06025P | | DED | | 050-099, 155-199, 275-299 |
| W0523 | 286T0523 | | | PLT C INSTR PNL TO SHELF | | | | | | | | | | | |
| 002 | 24 | PK | | 26-0 | 22-14-11 | D05453J | | 5 | | | D05455J | | 5 | | ALL |
| 003 | 22 | PA | | 26-0 | SPARE | D05453J | | 6 | | | D05455J | | 6 | | ALL |
| 004 | 22 | PA | | 26-0 | SPARE | D05453J | | 7 | | | D05455J | | 7 | | ALL |
| 005 | 22 | PA | | 26-0 | SPARE | D05453J | | 29 | | | D05455J | | 29 | | ALL |
| 006 | 22 | PA | | 26-0 | SPARE | D05453J | | 30 | | | D05455J | | 30 | | ALL |
| 007 | 22 | PA | | 26-0 | SPARE | D05453J | | 31 | | | D05455J | | 31 | | ALL |
| 008 | 22 | PA | | 28-0 | 34-22-36 | D05453J | | 23 | | | D05455J | | 23 | | ALL |
| 152 | 24 | PK | | 26-0 | 34-24-11 | D05453J | | 10 | | | D05455J | | 10 | | ALL |
| 153 | 24 | PK | | 26-0 | 34-24-11 | D05453J | | 13 | | | D05455J | | 13 | | ALL |
| 154 | 24 | PK | | 26-0 | 34-24-11 | D05453J | | 16 | | | D05455J | | 16 | | ALL |
| 155 | 24 | PK | | 26-0 | 34-24-11 | D05453J | | 19 | | | D05455J | | 19 | | ALL |
| 201B | 24 | PL | IA | 26-0 | 34-24-11 | D05453J | | 2 | | | D05455J | | 2 | | ALL |
| 201R | 24 | PL | IA | 0-0 | 34-24-11 | D05453J | | 1 | | | D05455J | | 1 | | ALL |
| 202B | 24 | PL | IB | 26-0 | 34-24-11 | D05453J | | 9 | | | D05455J | | 9 | | ALL |
| 202R | 24 | PL | IB | 0-0 | 34-24-11 | D05453J | | 8 | | | D05455J | | 8 | | ALL |
| 203B | 24 | PL | IC | 26-0 | 34-24-11 | D05453J | | 12 | | | D05455J | | 12 | | ALL |
| 203R | 24 | PL | IC | 0-0 | 34-24-11 | D05453J | | 11 | | | D05455J | | 11 | | ALL |
| 204B | 24 | PL | ID | 26-0 | 34-24-11 | D05453J | | 15 | | | D05455J | | 15 | | ALL |
| 204R | 24 | PL | ID | 0-0 | 34-24-11 | D05453J | | 14 | | | D05455J | | 14 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0520

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0523 | 286T0523 | | | PLT C INSTR PNL TO SHELF (continued) | | | | | | | | | | | | |
| 205B | 24 | PL | IE | 26-0 | 34-24-11 | D05453J | 18 | | | D05455J | 18 | | | ALL | | |
| 205R | 24 | PL | IE | 0-0 | 34-24-11 | D05453J | 17 | | | D05455J | 17 | | | ALL | | |
| 301B | 24 | PM | MA | 26-0 | 34-24-11 | D05453J | 21 | | | D05455J | 21 | | | ALL | | |
| 301R | 24 | PM | MA | 0-0 | 34-24-11 | D05453J | 20 | | | D05455J | 20 | | | ALL | | |
| 301Y | 24 | PM | MA | 0-0 | 34-24-11 | D05453J | 22 | | | D05455J | 22 | | | ALL | | |
| W0525 | 286T0525 | | | LT. STAB TRIM - BRKT. AC1402 TO CONTROL STAND P10 | | | | | | | | | | | | |
| 001Y | 20 | PJ | | 158-0 | 27-41-31 | D02263J | 6 | | | D06027P | 1 | | | 050-099 | | |
| 001Y | 20 | PJ | | 179-9 | 27-41-31 | D02263J | 6 | | | D06027P | 1 | | | 155-199, 275-299 | | |
| 002Y | 20 | PJ | | 158-0 | 27-41-31 | D02263J | 5 | | | D06027P | 2 | | | 050-099 | | |
| 002Y | 20 | PJ | | 179-9 | 27-41-31 | D02263J | 5 | | | D06027P | 2 | | | 155-199, 275-299 | | |
| 003Y | 20 | P5 | AC | 158-0 | 27-41-31 | D02263J | 10 | | | D06029P | 1 | | | 050-099 | | |
| 003Y | 20 | P5 | AC | 180-0 | 27-41-31 | D02263J | 10 | | | D06029P | 1 | | | 155-199, 275-299 | | |
| 003Z | | | AC | 0-0 | 27-41-31 | D02263J | DED | | | D06029P | DED | | | 050-099, 155-199, 275-299 | | |
| 004Y | 20 | P5 | AD | 158-0 | 27-41-31 | D02263J | 11 | | | D06029P | 2 | | | 050-099 | | |
| 004Y | 20 | P5 | AD | 180-0 | 27-41-31 | D02263J | 11 | | | D06029P | 2 | | | 155-199, 275-299 | | |
| 004Z | | | AD | 0-0 | 27-41-31 | D02263J | DED | | | D06029P | DED | | | 050-099, 155-199, 275-299 | | |
| 005 | 20 | PA | | 2-0 | 27-41-31 | D02263J | 8 | | | GD00603 | D.. | 2 | | 050-099 | | |
| 005 | 20 | PA | | 1-4 | 27-41-31 | D02263J | 8 | | | GD00603 | D.. | 2 | | 155-199, 275-299 | | |
| W0527 | 286T0527 | | | CAUTION & WRN SYS,FWD PNL TO SHELVES | | | | | | | | | | | | |
| 001 | 24 | PK | | 34-0 | 22-14-11 | D04879J | 1 | | | D04893J | 1 | | | ALL | | |
| 002 | 22 | PA | | 34-0 | SPARE | D04879J | 5 | | | D04893J | 5 | | | ALL | | |
| 003 | 24 | PK | | 34-0 | 22-14-11 | D04879J | 6 | | | D04893J | 6 | | | ALL | | |
| 008 | 22 | PA | | 34-0 | SPARE | D04879J | 2 | | | D04893J | 22 | | | ALL | | |
| 009 | 22 | PA | | 34-0 | 34-45-14 | D04893J | 7 | | | D04879J | 7 | | | 050-099, 150-199, 277-299 | | |
| 014 | 24 | PK | | 28-0 | 34-61-26 | D04893J | 9 | | | D04899J | 6 | | | 155-199, 277-299 | | |
| 014 | 24 | PK | | 33-0 | 34-61-26 | D04893J | 9 | | | D04899J | 6 | | | 275-276 | | |
| 016 | 24 | PK | | 28-0 | 34-61-16 | D04893J | 8 | | | D04899J | 16 | | | 050-099, 155-199, 277-299 | | |
| 016 | 24 | PK | | 33-0 | 34-61-16 | D04893J | 8 | | | D04899J | 16 | | | 275-276 | | |
| 025 | 22 | PA | | 35-0 | SPARE | D04893J | 35 | | | D04455J | 5 | | | ALL | | |
| 026 | 22 | PA | | 35-0 | SPARE | D04893J | 36 | | | D04455J | 6 | | | ALL | | |
| 027 | 22 | PA | | 28-0 | SPARE | D04893J | 37 | | | D04899J | 7 | | | ALL | | |
| 028 | 22 | PA | | 28-0 | SPARE | D04893J | 38 | | | D04899J | 8 | | | ALL | | |
| 029 | 24 | PK | | 28-0 | 34-61-25 | D04893J | 34 | | | D04899J | 20 | | | 050-099, 150-199 | | |

WIRE LIST

D280T132

91-21-11

Section W0520

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0527 | 286T0527 | | | CAUTION & WRN SYS,FWD PNL TO SHELVES (continued) | | | | | | | | | | | |
| 029 | 24 | | PK | | 28-0 | SPARE | D04893J | 34 | | | D04899J | 20 | | | 275-299 |
| 208B | 20 | | PR | IH | 28-0 | 34-12-21 | D04893J | 40 | | | D04899J | 18 | | | ALL |
| 208R | 20 | | PR | IH | 0-0 | 34-12-21 | D04893J | 39 | | | D04899J | 17 | | | ALL |
| 208Z | | | | IH | 0-0 | 34-12-21 | D04893J | 41 | | | D04899J | 19 | | | ALL |
| 209 | 20 | | UA | | 1-6 | 34-13-11 | D04893J | | | II | GD00553 | S.. | 2 | | ALL |
| 209B | 24 | | PW | II | 28-0 | 34-13-11 | D04893J | 45 | | | D04899J | 24 | | | ALL |
| 209R | 24 | | PW | II | 0-0 | 34-13-11 | D04893J | 44 | | | D04899J | 25 | | | ALL |
| 209Z | | | | II | 0-0 | 34-13-11 | D04893J | | | II | D04899J | 26 | | | ALL |
| 211 | 20 | | UA | | 1-6 | 34-22-81 | D04893J | | | IK | GD00553 | S.. | 2 | | ALL |
| 211B | 24 | | PW | IK | 35-0 | 34-22-81 | D04893J | 30 | | | D04455J | 14 | | | ALL |
| 211R | 24 | | PW | IK | 0-0 | 34-22-81 | D04893J | 29 | | | D04455J | 13 | | | ALL |
| 211Z | | | | IK | 0-0 | 34-22-81 | D04893J | | | IK | D04455J | 15 | | | ALL |
| 213 | 20 | | UA | | 1-6 | 34-22-91 | D04893J | | | FM | GD00553 | S.. | 2 | | 050-099, 150-156, 162-166 |
| 213 | 20 | | UA | | 1-6 | SPARE | D04893J | | | FM | GD00553 | S.. | 2 | | 157, 167-199, 275-276 |
| 213B | 24 | | PW | IM | 35-0 | 34-22-91 | D04893J | 50 | | | D04455J | 17 | | | 050-099, 150-156, 162-166 |
| 213B | 24 | | PW | IM | 35-0 | SPARE | D04893J | 50 | | | D04455J | 17 | | | 157, 167-199, 275-276 |
| 213R | 24 | | PW | IM | 0-0 | 34-22-91 | D04893J | 49 | | | D04455J | 16 | | | 050-099, 150-156, 162-166 |
| 213R | 24 | | PW | IM | 0-0 | SPARE | D04893J | 49 | | | D04455J | 16 | | | 157, 167-199, 275-276 |
| 213Z | | | | IM | 0-0 | 34-22-91 | D04893J | | | FM | D04455J | 18 | | | 050-099, 150-156, 162-166 |
| 213Z | | | | IM | 0-0 | SPARE | D04893J | | | FM | D04455J | 18 | | | 157, 167-199, 275-276 |
| 214 | 20 | | UA | | 1-6 | 34-22-91 | D04893J | | | FN | GD00553 | S.. | 2 | | ALL |
| 214B | 24 | | PW | IN | 35-0 | 34-22-91 | D04893J | 53 | | | D04455J | 20 | | | ALL |
| 214R | 24 | | PW | IN | 0-0 | 34-22-91 | D04893J | 52 | | | D04455J | 19 | | | ALL |
| 214Z | | | | IN | 0-0 | 34-22-91 | D04893J | | | FN | D04455J | 21 | | | ALL |
| 216B | 24 | | PW | IP | 34-0 | SPARE | D04893J | 3 | | | D04879J | 9 | | | 153-154 |
| 216R | 24 | | PW | IP | 0-0 | SPARE | D04893J | 2 | | | D04879J | 8 | | | 153-154 |
| 216Z | | | | IP | 0-0 | SPARE | D04893J | 4 | | | D04879J | 10 | | | 153-154 |
| 217 | 20 | | UA | | 3-0 | 34-45-14 | D04893J | | | IQ | GD00553 | S.. | 2 | | 050-099, 153-199, 277-299 |
| 217 | 20 | | UA | | 3-0 | 34-45-14 | D04893J | | | IQ | GD04510 | S.. | 2 | | 150-152 |
| 217B | 24 | | PW | IQ | 35-0 | 34-45-14 | D04893J | 18 | | | D04455J | 2 | | | 050-099, 150-199, 277-299 |
| 217R | 24 | | PW | IQ | 0-0 | 34-45-14 | D04893J | 17 | | | D04455J | 1 | | | 050-099, 150-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0520
Page 3
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|---|-------------|---------|----------|---------|------|--------|-------|------|------|---------|-----|-------------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0527 | 286T0527 | | | CAUTION & WRN SYS,FWD PNL TO SHELVES (continued) | | | | | | | | | | | | | |
| 217Z | | | | | IQ | 0-0 | 34-45-14 | D04893J | | | | | IQ | D04455J | 3 | | 050-099, 150-199, 277-299 |
| 218 | 20 | | UA | | | 1-6 | 34-22-91 | D04893J | REF | | | | IR | GD00553 | S.. | 2 | 157, 167-199, 275-299 |
| 218B | 24 | | PW | IR | | 28-0 | 34-22-91 | D04893J | 26 | | | | | D04899J | 28 | | 157, 167-199, 277-299 |
| 218B | 24 | | PW | IR | | 33-0 | 34-22-91 | D04893J | 26 | | | | | D04899J | 28 | | 275-276 |
| 218R | 24 | | PW | IR | | 0-0 | 34-22-91 | D04893J | 25 | | | | | D04899J | 27 | | 157, 167-199, 275-299 |
| 218Z | | | | IR | | 0-0 | 34-22-91 | D04893J | REF | | | | IR | D04899J | 29 | | 157, 167-199, 275-299 |
| FRI | | | | | | 0-0 | 34-13-11 | D04893J | | | | | II | D04893J | 46 | | ALL |
| FRK | | | | | | 0-0 | 34-22-81 | D04893J | | | | | IK | D04893J | 31 | | ALL |
| FRM | | | | | | 0-0 | 34-22-91 | D04893J | | | | | FM | D04893J | 51 | | 050-099, 150-156, 162-166 |
| FRM | | | | | | 0-0 | SPARE | D04893J | | | | | FM | D04893J | 51 | | 157, 167-199, 275-276 |
| FRN | | | | | | 0-0 | 34-22-91 | D04893J | | | | | FN | D04893J | 54 | | ALL |
| FRQ | | | | | | 0-0 | 34-45-14 | D04893J | | | | | IQ | D04893J | 19 | | 050-099, 150-199, 277-299 |
| FRR | | | | | | 0-0 | 34-22-91 | D04893J | REF | | | | IR | D04893J | 27 | | 157, 167-199, 275-276 |
| W0529 | 286T0529 | | | AFDS WRN AND ANN R,P3 TO SHELF | | | | | | | | | | | | | |
| 004 | 22 | | PA | | | 28-0 | SPARE | D05557J | 4 | | | | | D05555J | 4 | | ALL |
| 005 | 24 | | PK | | | 28-0 | 34-21-31 | D05557J | 5 | | | | | D05555J | 5 | | ALL |
| 006 | 22 | | PA | | | 28-0 | SPARE | D05557J | 1 | | | | | D05555J | 1 | | ALL |
| 007 | 22 | | PA | | | 28-0 | SPARE | D05557J | 2 | | | | | D05555J | 2 | | ALL |
| 008 | 22 | | PA | | | 28-0 | SPARE | D05557J | 3 | | | | | D05555J | 3 | | ALL |
| 009 | 22 | | PA | | | 28-0 | SPARE | D05557J | 6 | | | | | D05555J | 6 | | ALL |
| 010 | 24 | | PK | | | 28-0 | 22-14-21 | D05557J | 18 | | | | | D05555J | 18 | | ALL |
| 011 | 24 | | PK | | | 28-0 | 22-14-21 | D05557J | 19 | | | | | D05555J | 19 | | ALL |
| 012 | 22 | | PA | | | 28-0 | 22-14-21 | D05557J | 20 | | | | | D05555J | 20 | | ALL |
| 201B | 22 | | PB | IA | | 28-0 | 34-12-11 | D05557J | 22 | | | | | D05555J | 22 | | ALL |
| 201R | 22 | | PB | IA | | 0-0 | 34-12-11 | D05557J | 21 | | | | | D05555J | 21 | | ALL |
| 208B | 22 | | PB | IH | | 28-0 | SPARE | D05557J | 9 | | | | | D05555J | 9 | | ALL |
| 208R | 22 | | PB | IH | | 0-0 | SPARE | D05557J | 8 | | | | | D05555J | 8 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0520

Page 4 End

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0533 | 286T0533 | | | 3 AXIS ACCELERATION XDCR-MAIN W/W AREA | | | | | | | | | | | |
| 201B | 20 | | VG | A | 10-10 | 31-31-13 | D00321 | | D | | D04727P | | 5 | | ALL |
| 201R | 20 | | VG | A | 0-0 | 31-31-13 | D00321 | | C | | D04727P | | 4 | | ALL |
| 201Z | | | | A | 0-0 | 31-31-13 | D00321 | | DED | | D04727P | | | FA | ALL |
| 202B | 20 | | VG | B | 10-10 | 31-31-13 | D00321 | | F | | D04727P | | 7 | | ALL |
| 202R | 20 | | VG | B | 0-0 | 31-31-13 | D00321 | | E | | D04727P | | 6 | | ALL |
| 202Z | | | | B | 0-0 | 31-31-13 | D00321 | | DED | | D04727P | | | FA | ALL |
| 203B | 20 | | VG | C | 10-10 | 31-31-13 | D00321 | | H | | D04727P | | 9 | | ALL |
| 203R | 20 | | VG | C | 0-0 | 31-31-13 | D00321 | | G | | D04727P | | 8 | | ALL |
| 203Z | | | | C | 0-0 | 31-31-13 | D00321 | | DED | | D04727P | | | FA | ALL |
| 204B | 20 | | UB | D | 10-10 | 31-31-13 | D00321 | | B | | D04727P | | 2 | | ALL |
| 204R | 20 | | UB | D | 0-0 | 31-31-13 | D00321 | | A | | D04727P | | 1 | | ALL |
| FRA | | | | | 0-0 | 31-31-13 | D04727P | | 3 | | D04727P | | | FA | ALL |
| W0539 | 286T0539 | | | YAW DAMPER L, TAIL DISC TO PCA | | | | | | | | | | | |
| 001 | 20 | | UA | | 33-0 | 31-51-41 | D04783J | | 1 | | D00175 | | 22 | | ALL |
| 002 | 18 | | UA | | 2-10 | 31-51-41 | GD00613 | | D.. | N | D00175 | | 23 | DK | ALL |
| 004 | 18 | | UA | | 2-11 | 27-58-21 | GD00577 | | S.. | N | D00175 | | 31 | DK | ALL |
| 203B | 20 | | UB | IC | 33-0 | 27-58-21 | D04783J | | 11 | | D00175 | | 1 | | ALL |
| 203R | 20 | | UB | IC | 0-0 | 27-58-21 | D04783J | | 12 | | D00175 | | 7 | | ALL |
| 302B | 20 | | UC | MB | 33-0 | 27-58-21 | D04783J | | 13 | | D00175 | | 2 | | ALL |
| 302R | 20 | | UC | MB | 0-0 | 27-58-21 | D04783J | | 14 | | D00175 | | 3 | | ALL |
| 302Y | 20 | | UC | MB | 0-0 | 27-58-21 | D04783J | | 15 | | D00175 | | 4 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0530
Page 1 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0546 | 286T0546 | | | ENGINE FIRE EXTINGUISHING BOTTLE 1 | | | | | | | | | | | | |
| 001R | 20 | | PH | 3-0 | 26-21-11 | D01428 | | 1 | | | D06886J | | 3 | | | 050-099, 155-199, 275-299 |
| 002R | 20 | | PH | 2-0 | 26-21-11 | D01424 | | 1 | | | D06886J | | 5 | | | 050-099, 155-199, 275-299 |
| 003R | 20 | | PH | 2-0 | 26-21-11 | D01430 | | 1 | | | D06886J | | 7 | | | 050-099, 155-199, 275-299 |
| 004R | 20 | | PH | 4-0 | 26-21-11 | D01428 | | 3 | | | GD05842 | D.. | E | * | | 050-099 |
| 004R | 20 | | PH | 3-0 | 26-21-11 | D01428 | | 3 | | | GD05862 | D.. | E | * | | 155-199, 275-299 |
| 005R | 20 | | PH | 2-0 | 26-21-11 | D01424 | | 2 | | | GD05842 | D.. | E | * | | 050-099 |
| 005R | 20 | | PH | 2-0 | 26-21-11 | D01424 | | 2 | | | GD05862 | D.. | E | * | | 155-199, 275-299 |
| 006R | 20 | | PH | 3-0 | 26-21-11 | D01430 | | 2 | | | GD05842 | D.. | E | * | | 050-099 |
| 006R | 20 | | PH | 3-0 | 26-21-11 | D01430 | | 2 | | | GD05862 | D.. | E | * | | 155-199, 275-299 |
| 007R | 20 | | PH | 4-0 | 26-21-11 | D01428 | | 4 | | | GD05844 | S.. | E | * | | 050-099 |
| 007R | 20 | | PH | 4-0 | 26-21-11 | D01428 | | 4 | | | GD05864 | S.. | E | * | | 155-199, 275-299 |
| 008R | 20 | | PH | 2-0 | 26-21-11 | D01424 | | 3 | | | GD05844 | S.. | E | * | | 050-099 |
| 008R | 20 | | PH | 2-0 | 26-21-11 | D01424 | | 3 | | | GD05864 | S.. | E | * | | 155-199, 275-299 |
| 009R | 20 | | PH | 3-0 | 26-21-11 | D01430 | | 3 | | | GD05844 | S.. | E | * | | 050-099 |
| 009R | 20 | | PH | 3-0 | 26-21-11 | D01430 | | 3 | | | GD05864 | S.. | E | * | | 155-199, 275-299 |
| W0548 | 286T0548 | | | ENGINE FIRE EXTINGUISHING BOTTLE 2 | | | | | | | | | | | | |
| 001R | 20 | | PH | 2-0 | 26-21-11 | D01434 | | 1 | | | D06888J | | 6 | | | 050-099, 155-199, 275-299 |
| 002R | 20 | | PH | 3-0 | 26-21-11 | D01426 | | 1 | | | D06888J | | 9 | | | 050-099, 155-199, 275-299 |
| 003R | 20 | | PH | 4-0 | 26-21-11 | D01432 | | 1 | | | D06888J | | 12 | | | 050-099, 155-199, 275-299 |
| 004R | 20 | | PH | 3-0 | 26-21-11 | D01434 | | 3 | | | GD05846 | D.. | E | * | | 050-099 |
| 004R | 20 | | PH | 3-0 | 26-21-11 | D01434 | | 3 | | | GD05866 | D.. | E | * | | 155-199, 275-299 |
| 005R | 20 | | PH | 4-0 | 26-21-11 | D01426 | | 2 | | | GD05846 | D.. | E | * | | 050-099 |
| 005R | 20 | | PH | 4-0 | 26-21-11 | D01426 | | 2 | | | GD05866 | D.. | E | * | | 155-199, 275-299 |
| 006R | 20 | | PH | 5-0 | 26-21-11 | D01432 | | 2 | | | GD05846 | D.. | E | * | | 050-099 |
| 006R | 20 | | PH | 5-0 | 26-21-11 | D01432 | | 2 | | | GD05866 | D.. | E | * | | 155-199, 275-299 |
| 007R | 20 | | PH | 3-0 | 26-21-11 | D01434 | | 4 | | | GD05848 | S.. | E | * | | 050-099 |
| 007R | 20 | | PH | 3-0 | 26-21-11 | D01434 | | 4 | | | GD05868 | S.. | E | * | | 155-199, 275-299 |
| 008R | 20 | | PH | 4-0 | 26-21-11 | D01426 | | 3 | | | GD05848 | S.. | E | * | | 050-099 |
| 008R | 20 | | PH | 4-0 | 26-21-11 | D01426 | | 3 | | | GD05868 | S.. | E | * | | 155-199, 275-299 |
| 009R | 20 | | PH | 5-0 | 26-21-11 | D01432 | | 3 | | | GD05848 | S.. | E | * | | 050-099 |
| 009R | 20 | | PH | 5-0 | 26-21-11 | D01432 | | 3 | | | GD05868 | S.. | E | * | | 155-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0540

Page 1 End

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0571 | 286T0571 | | | SERVICE INTERPHONE-JACK SCREW SERVICE | | | | | | | | | | | |
| 201B | 20 | VG | | A | 22-4 | 23-41-11 | SP00187 | | S | | SM00002 | | 9 | | ALL |
| 201R | 20 | VG | | A | 0-0 | 23-41-11 | SP00185 | | S | | SM00001 | | 9 | | ALL |
| 201Z | | | | A | 0-0 | 23-41-11 | SP00189 | | S | | SM00003 | | 9 | | ALL |
| A-A | | | | B | 0-0 | 23-41-11 | D08503 | RED | | | SM00001 | | 9 | | ALL |
| A-B | | | | B | 0-0 | 23-41-11 | D08503 | BLU | | | SM00002 | | 9 | | ALL |
| A-C | | | | B | 0-0 | 23-41-11 | D08503 | BLK | | | SM00003 | | 9 | | ALL |
| W0572 | 286T0572 | | | AIR COND RIGHT PACK ELEC HYD PUMP CONTROL & INDICATION | | | | | | | | | | | |
| 001 | 22 | PA | | | 18-9 | 28-42-11 | D04708P | | 1 | | D05506P | | 1 | | ALL |
| 003 | 24 | PK | | | 32-9 | 28-22-11 | D04708P | | 3 | | D04662P | | 3 | | ALL |
| 004 | 24 | PK | | | 32-9 | 28-22-11 | D04708P | | 4 | | D04662P | | 4 | | ALL |
| 005 | 22 | PA | | | 32-9 | 28-42-11 | D04708P | | 5 | | D04662P | | 5 | | ALL |
| 010 | 22 | PA | | | 31-8 | 30-34-11 | D04708P | | 10 | | D05798P | | 4 | | ALL |
| 011 | 24 | PK | | | 32-11 | 28-22-12 | D04708P | | 11 | | D05658P | | 55 | | 050-099, 155-199, 276-299 |
| 013 | 24 | PK | | | 17-4 | 21-53-22 | D08068P | | 10 | | D05506P | | 32 | | ALL |
| 014 | 22 | PA | | | 18-9 | 28-42-12 | D04708P | | 14 | | D05506P | | 3 | | ALL |
| 016 | 22 | PA | | | 18-9 | 29-11-31 | D04708P | | 16 | | D05506P | | 16 | | ALL |
| 017 | 24 | PK | | | 31-8 | 29-11-22 | D04708P | | 17 | | D05798P | | 36 | | ALL |
| 018 | 22 | PA | | | 31-8 | 29-11-22 | D04708P | | 18 | | D05798P | | 33 | | ALL |
| 019 | 22 | PA | | | 31-8 | 29-11-22 | D04708P | | 19 | | D05798P | | 28 | | ALL |
| 020 | 22 | PA | | | 31-8 | 29-11-22 | D04708P | | 20 | | D05798P | | 34 | | ALL |
| 021 | 24 | PK | | | 31-8 | 29-11-22 | D04708P | | 21 | | D05798P | | 30 | | ALL |
| 022 | 24 | PK | | | 17-4 | 21-53-22 | D08068P | | 11 | | D05506P | | 33 | | ALL |
| 023 | 24 | PK | | | 17-4 | 21-53-22 | D08068P | | 12 | | D05506P | | 34 | | ALL |
| 025 | 24 | PK | | | 16-0 | 29-11-22 | D05798P | | 51 | | D05506P | | 25 | | ALL |
| 026 | 22 | PA | | | 16-0 | 29-11-22 | D05798P | | 52 | | D05506P | | 26 | | ALL |
| 027 | 24 | PK | | | 16-0 | 29-11-22 | D05798P | | 53 | | D05506P | | 27 | | ALL |
| 028 | 22 | PA | | | 16-0 | 29-11-22 | D05798P | | 55 | | D05506P | | 28 | | ALL |
| 030 | 20 | PA | | | 12-4 | 29-11-22 | D05798P | | 54 | | GD00670 | | D.. | 2 | ALL |
| 037 | 24 | PK | | | 17-4 | 21-53-22 | D08068P | | 13 | | D05506P | | 35 | | ALL |
| 040 | 20 | PA | | | 32-9 | 21-61-71 | D04708P | | 23 | | D04662P | | 17 | | ALL |
| 041 | 20 | PA | | | 32-11 | 28-31-11 | D04708P | | 24 | | D05658P | | 51 | | 050-099, 155-199, 276-299 |
| 041 | 20 | PA | | | 32-9 | SPARE | D04708P | | 24 | | D04662P | | 18 | | 150-154, 275 |
| 042 | 20 | PA | | | 17-1 | 21-61-51 | D05506P | | 8 | | D04662P | | 19 | | ALL |
| 043 | 20 | PA | | | 17-1 | SPARE | D05506P | | 20 | | D04662P | | 20 | | 050-099, 150-155, 162-165 |
| 043 | 20 | PA | | | 17-1 | SPARE | D05506P | | 20 | | D04662P | CAP | Y | | 156-157, 166-199 |

WIRE LIST
D280T132

91-21-11
Section W0570
Page 1
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0572 | 286T0572 | | | AIR COND RIGHT PACK ELEC HYD PUMP CONTROL & INDICATION (continued) | | | | | | | | | | | |
| 044 | 24 | | PK | 32-9 | 21-58-12 | D04708P | | 25 | | | D04662P | | 16 | | ALL |
| 047 | 24 | | PK | 31-8 | 21-53-22 | D04708P | | 22 | | | D05798P | | 37 | | ALL |
| 048 | 24 | | PK | 31-8 | 21-53-22 | D04708P | | 15 | | | D05798P | | 1 | | ALL |
| 049 | 24 | | PK | 30-4 | 21-53-22 | D08068P | | 1 | | | D05798P | | 57 | | ALL |
| 050 | 24 | | PK | 30-4 | 21-53-22 | D08068P | | 2 | | | D05798P | | 58 | | ALL |
| 051 | 24 | | PK | 30-4 | 21-53-22 | D08068P | | 3 | | | D05798P | | 59 | | ALL |
| 052 | 24 | | PK | 30-4 | 21-53-22 | D08068P | | 4 | | | D05798P | | 60 | | ALL |
| 053 | 24 | | PK | 30-4 | 21-53-22 | D08068P | | 5 | | | D05798P | | 61 | | ALL |
| 054 | 24 | | PK | 30-4 | 21-53-22 | D08068P | | 6 | | | D05798P | | 56 | | ALL |
| 055 | 24 | | PK | 17-4 | 21-53-22 | D08068P | | 7 | | | D05506P | | 17 | | ALL |
| 056 | 24 | | PK | 17-4 | 21-53-22 | D08068P | | 8 | | | D05506P | | 30 | | ALL |
| 057 | 24 | | PK | 17-4 | 21-53-22 | D08068P | | 9 | | | D05506P | | 31 | | ALL |
| 058 | 24 | | PK | 24-10 | SPARE | D04708P | | 44 | | | D08068P | | 14 | | ALL |
| 059 | 24 | | PK | 32-11 | 21-26-11 | D04708P | | 45 | | | D05658P | | 1 | | ALL |
| 060 | 24 | | PK | 17-4 | 21-26-11 | D05506P | | 4 | | | D08068P | | 15 | | ALL |
| 062 | 24 | | PK | 31-6 | 21-26-11 | D08068P | | 16 | | | D05658P | | 3 | | ALL |
| 064 | 24 | | PK | 31-6 | 21-26-11 | D08068P | | 18 | | | D05658P | | 5 | | ALL |
| 065 | 24 | | PK | 31-6 | 21-26-11 | D08068P | | 19 | | | D05658P | | 6 | | ALL |
| 070 | 24 | | PK | 32-9 | 21-58-11 | D04708P | | 52 | | | D04662P | | 47 | | ALL |
| 072 | 24 | | PK | 43-7 | 21-58-12 | D03074 | | 1 | | | D04662P | | 15 | | 050-099, 150-154, 275-299 |
| 072 | 24 | | PV | 43-7 | 21-58-12 | D03074 | | 1 | | | D04662P | | 15 | | 155-199 |
| 072Z | | | CV | 0-0 | 21-58-12 | D03074 | | DED | | | D04662P | | DED | | 155-199 |
| 073 | 20 | | PA | 2-0 | 21-58-12 | D03074 | | 2 | | | GD03980 | | D.. | 2 | 050-099, 150-154, 275-299 |
| 073 | 20 | | PQ | 2-0 | 21-58-12 | D03074 | | 2 | | | GD03980 | | D.. | 2 | 155-199 |
| 073Z | | | CW | 0-0 | 21-58-12 | D03074 | | DED | | | GD03980 | | DED | | 155-199 |
| 081 | 24 | | PK | 17-4 | SPARE | D08068P | | 20 | | | D05506P | | 40 | | 150-199 |
| 083 | 24 | | PK | 20-6 | 21-61-51 | D05726P | | 22 | | | D08092J | | 27 | | ALL |
| 085 | 24 | | PK | 33-3 | 36-11-11 | D05726P | | 23 | | | D05658P | | 16 | | ALL |
| 086 | 24 | | PK | 33-3 | 36-11-11 | D05726P | | 24 | | | D05658P | | 17 | | ALL |
| 087 | 24 | | PK | 33-3 | 36-11-11 | D05726P | | 25 | | | D05658P | | 18 | | ALL |
| 088 | 22 | | PA | 33-3 | 36-11-11 | D05726P | | 26 | | | D05658P | | 19 | | ALL |
| 089 | 22 | | PA | 33-3 | 36-11-11 | D05726P | | 27 | | | D05658P | | 20 | | ALL |
| 090 | 24 | | PK | 33-3 | 36-11-31 | D05726P | | 28 | | | D05658P | | 21 | | ALL |
| 091 | 24 | | PK | 33-3 | 36-11-31 | D05726P | | 29 | | | D05658P | | 22 | | ALL |
| 092 | 24 | | PK | 33-3 | 36-11-31 | D05726P | | 30 | | | D05658P | | 23 | | ALL |
| 093 | 22 | | PA | 33-3 | 36-11-31 | D05726P | | 31 | | | D05658P | | 24 | | ALL |
| 094 | 22 | | PA | 33-3 | 36-11-31 | D05726P | | 32 | | | D05658P | | 25 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0570

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0572 | 286T0572 | | | AIR COND RIGHT PACK ELEC HYD PUMP CONTROL & INDICATION (continued) | | | | | | | | | | | |
| 095 | 22 | | PA | | 32-1 | 36-11-51 | D05798P | 22 | | | D05726P | 34 | | | ALL |
| 096 | 22 | | PA | | 25-2 | 36-11-51 | D05726P | 35 | | | D08068P | 22 | | | ALL |
| 097 | 24 | | PK | | 25-2 | 36-11-51 | D05726P | 36 | | | D08068P | 23 | | | ALL |
| 098 | 24 | | PK | | 18-9 | 36-11-51 | D08068P | 26 | | | D08092J | 23 | | | ALL |
| 099 | 18 | | PA | | 16-10 | 36-11-51 | D05658P | 12 | DK | | D08092J | 24 | DK | | ALL |
| 100 | 18 | | PA | | 16-10 | 36-11-51 | D05658P | 11 | DK | | D08092J | 32 | DK | | ALL |
| 101 | 24 | | PK | | 16-10 | 36-11-51 | D05658P | 26 | | | D08092J | 29 | | | ALL |
| 102 | 18 | | PA | | 16-10 | 36-11-51 | D05658P | 27 | DK | | D08092J | 34 | DK | | 150-154, 275 |
| 103 | 24 | | PK | | 16-10 | 36-11-51 | D05658P | 28 | | | D08092J | 28 | | | ALL |
| 105 | 24 | | PK | | 16-10 | 36-11-51 | D05658P | 30 | | | D08092J | 30 | | | ALL |
| 106 | 18 | | PA | | 31-6 | 36-11-51 | D05658P | 31 | DK | | D08068P | 28 | DL | | ALL |
| 107 | 24 | | PK | | 31-6 | 36-11-51 | D05658P | 29 | | | D08068P | 29 | | | ALL |
| 108 | 18 | | PA | | 31-6 | 36-11-51 | D05658P | 33 | DK | | D08068P | 27 | DL | | ALL |
| 110 | 22 | | PA | | 30-4 | 36-11-51 | D05798P | 19 | | | D08068P | 24 | | | ALL |
| 112 | 24 | | PK | | 33-2 | 36-11-61 | D05726P | 39 | | | D04662P | 1 | | | 050-099, 150-156, 162-166, 275-276 |
| 112 | 24 | | PK | | 25-2 | 36-11-61 | D05726P | 39 | | | D08068P | 35 | | | 157, 167-199, 277-299 |
| 113 | 22 | | PA | | 25-2 | 36-11-61 | D05726P | 38 | | | D08068P | 36 | | | ALL |
| 114 | 18 | | PA | | 40-0 | 36-11-61 | D08068P | 31 | DL | | D04662P | 42 | DL | | 050-099, 155-156, 162-166, 275-276 |
| 114 | 18 | | PA | | 40-0 | 36-11-61 | D08068P | 31 | DL | | D04662P | 42 | DK | | 150-154 |
| 114 | 18 | | PA | | 31-5 | 36-11-61 | D08068P | 31 | DL | | D04662P | 42 | DL | | 157, 167-199, 277-299 |
| 115 | 24 | | PK | | 16-7 | 36-11-61 | D04662P | 40 | | | D05782J | 2 | | | ALL |
| 116 | 24 | | PK | | 16-7 | 36-11-61 | D04662P | 41 | | | D05782J | 3 | | | ALL |
| 118 | 18 | | PA | | 16-7 | 36-11-61 | D04662P | 43 | DL | | D05782J | 5 | DL | | 050-099, 150-155, 162-165, 275-276 |
| 118 | 18 | | PA | | 16-7 | 36-11-61 | D04662P | 43 | DL | | D05782J | 14 | DL | | 156, 166 |
| 119 | 24 | | PK | | 16-7 | 36-11-61 | D04662P | 44 | | | D05782J | 6 | | | ALL |
| 120 | 24 | | PK | | 16-7 | 36-11-61 | D04662P | 45 | | | D05782J | 7 | | | ALL |
| 121 | 24 | | PK | | 16-7 | 36-11-61 | D04662P | 46 | | | D05782J | 8 | | | ALL |
| 123 | 24 | | PK | | 16-7 | 36-11-61 | D04662P | 48 | | | D05782J | 11 | | | ALL |
| 126 | 24 | | PK | | 18-8 | 36-11-61 | D05782J | 12 | | | D08068P | 32 | | | ALL |
| 127 | 18 | | PA | | 18-8 | 36-11-61 | D05782J | 13 | DL | | D08068P | 33 | DL | | 050-099, 150-156, 162-166, 275-276 |
| 127 | 18 | | PA | | 31-5 | 36-11-61 | D04662P | 43 | DL | | D08068P | 33 | DL | | 157, 167-199, 277-299 |
| 128 | 24 | | PK | | 31-5 | 36-11-61 | D04662P | 49 | | | D08068P | 34 | | | ALL |
| 134 | 24 | | PK | | 33-3 | 36-21-11 | D05726P | 9 | | | D05658P | 37 | | | ALL |
| 135 | 24 | | PK | | 17-1 | 21-58-11 | D04662P | 9 | | | D05506P | 38 | | | ALL |
| 136 | 24 | | PK | | 33-2 | 36-11-41 | D05726P | 15 | | | D04662P | 2 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0570
Page 3
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-----|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0572 | 286T0572 | | | AIR COND RIGHT PACK ELEC HYD PUMP CONTROL & INDICATION (continued) | | | | | | | | | | | | | |
| 137 | 24 | | PK | 19-1 | 36-11-41 | D05506P | | 47 | | | | | D05726P | 14 | | | ALL |
| 138 | 24 | | PK | 17-3 | 21-61-21 | D05506P | | 7 | | | | | D05658P | 32 | | | ALL |
| 139 | 18 | | PA | 33-3 | 36-11-51 | D05726P | | 33 | DL | | | | D05658P | 27 | DK | | 050-099, 155, 162-165, 276 |
| 139 | 22 | | PA | 32-1 | SPARE | D05726P | | | CAP | Y | | | D05798P | 18 | | | 150-154, 275 |
| 139 | 18 | | PA | 33-3 | SPARE | D05726P | | 33 | DL | | | | D05658P | 27 | DK | | 156-157, 166-199, 277-299 |
| 140 | 24 | | PK | 30-4 | 36-11-51 | D08068P | | 25 | | | | | D05798P | 17 | | | ALL |
| 142 | 24 | | PK | 25-2 | 36-11-51 | D05726P | | 10 | | | | | D08068P | 40 | | | ALL |
| 143 | 22 | | PA | 18-9 | 36-11-51 | D08092J | | 38 | | | | | D08068P | 41 | | | ALL |
| 144 | 22 | | PA | 18-9 | 36-11-51 | D08092J | | 39 | | | | | D08068P | 42 | | | ALL |
| 149 | 24 | | PK | 32-9 | 28-42-31 | D04708P | | 9 | | | | | D04662P | 7 | | | ALL |
| 152 | 24 | | PK | 32-1 | 30-31-11 | D05726P | | 42 | | | | | D05798P | 9 | | | ALL |
| 153 | 22 | | PA | 32-1 | 30-31-21 | D05726P | | 43 | | | | | D05798P | 10 | | | ALL |
| 154 | 22 | | PA | 32-1 | 30-31-23 | D05726P | | 44 | | | | | D05798P | 11 | | | ALL |
| 155 | 24 | | PK | 32-1 | 30-31-11 | D05726P | | 45 | | | | | D05798P | 12 | | | ALL |
| 156 | 24 | | PK | 32-1 | 30-31-11 | D05726P | | 46 | | | | | D05798P | 13 | | | ALL |
| 162 | 22 | | PA | 32-1 | 30-31-11 | D05726P | | 52 | | | | | D05798P | 8 | | | ALL |
| 165 | 22 | | PA | 32-1 | 30-31-13 | D05726P | | 55 | | | | | D05798P | 20 | | | ALL |
| 169 | 18 | | PA | 10-1 | SPARE | D05798P | | 5 | DK | | | | D04662P | | CAP | Y | 050-099, 150-156, 162-166 |
| 169 | 18 | | PA | 16-0 | SPARE | D05798P | | 5 | DK | | | | D04662P | | CAP | Y | 275-276 |
| 170 | 18 | | PA | 15-6 | SPARE | D05798P | | 27 | DK | | | | D05782J | 15 | DL | | 050-099, 155-156, 162-166, 275-276 |
| 170 | 18 | | PA | 15-6 | SPARE | D05798P | | 27 | DK | | | | D05782J | | CAP | Y | 150-154 |
| 178 | 22 | | PA | 31-8 | 30-32-21 | D04708P | | 2 | | | | | D05798P | 31 | | | ALL |
| 179 | 22 | | PA | 21-3 | 30-33-11 | SP02314 | | | | 9 | | | D05798P | 32 | | | ALL |
| 192 | 12 | | PA | 32-8 | 21-58-14 | D05910P | | 1 | | | | | D06286P | 1 | | | ALL |
| 193 | 12 | | PA | 32-8 | 21-58-14 | D05910P | | 2 | | | | | D06286P | 2 | | | ALL |
| 194 | 12 | | PA | 32-8 | 21-58-14 | D05910P | | 3 | | | | | D06286P | 3 | | | ALL |
| 195 | 24 | | PK | 10-2 | 21-44-21 | D05798P | | 47 | | | | | D05658P | 8 | | | ALL |
| 204B | 22 | | PB | D | 20-2 | 21-51-12 | D08092J | | 1 | | | | D04708P | 33 | | | ALL |
| 204R | 22 | | PB | D | 0-0 | 21-51-12 | D08092J | | 2 | | | | D04708P | 34 | | | ALL |
| 205B | 24 | | PL | F | 20-6 | 21-61-11 | D05726P | | 1 | | | | D08092J | 15 | | | ALL |
| 205R | 24 | | PL | F | 0-0 | 21-61-11 | D05726P | | 2 | | | | D08092J | 16 | | | ALL |
| 206B | 24 | | PL | G | 20-6 | 21-61-11 | D05726P | | 3 | | | | D08092J | 17 | | | ALL |
| 206R | 24 | | PL | G | 0-0 | 21-61-11 | D05726P | | 4 | | | | D08092J | 18 | | | ALL |
| 207B | 24 | | PL | H | 20-6 | 21-61-21 | D05726P | | 5 | | | | D08092J | 19 | | | ALL |
| 207R | 24 | | PL | H | 0-0 | 21-61-21 | D05726P | | 6 | | | | D08092J | 20 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0570

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0572 | 286T0572 | | | AIR COND RIGHT PACK ELEC HYD PUMP CONTROL & INDICATION (continued) | | | | | | | | | | | |
| 208B | 24 | PL | J | 20-6 | 21-61-21 | D05726P | | 7 | | D08092J | | 21 | | ALL | |
| 208R | 24 | PL | J | 0-0 | 21-61-21 | D05726P | | 8 | | D08092J | | 22 | | ALL | |
| 212B | 24 | PL | O | 33-3 | 36-21-11 | D05726P | | 41 | | D05658P | | 39 | | ALL | |
| 212R | 24 | PL | O | 0-0 | 36-21-11 | D05726P | | 40 | | D05658P | | 38 | | ALL | |
| 216B | 24 | PL | AF | 3-10 | 21-51-12 | D05506P | | 53 | | D05782J | | 18 | | ALL | |
| 216R | 24 | PL | AF | 0-0 | 21-51-12 | D05506P | | 54 | | D05782J | | 19 | | ALL | |
| 219B | 22 | PB | AI | 15-6 | 21-51-12 | D05798P | | 39 | | D05782J | | 21 | | ALL | |
| 219R | 22 | PB | AI | 0-0 | 21-51-12 | D05798P | | 38 | | D05782J | | 20 | | ALL | |
| 220B | 22 | PB | AJ | 3-10 | 21-51-23 | D06264J | | 6 | | D05506P | | 18 | | ALL | |
| 220R | 22 | PB | AJ | 0-0 | 21-51-23 | D06264J | | 7 | | D05506P | | 19 | | ALL | |
| 221B | 22 | PB | AK | 3-10 | 21-51-23 | D06264J | | 4 | | D05506P | | 48 | | ALL | |
| 221R | 22 | PB | AK | 0-0 | 21-51-23 | D06264J | | 5 | | D05506P | | 49 | | ALL | |
| 222B | 22 | PB | AL | 15-6 | 21-51-12 | D05798P | | 40 | | D05782J | | 22 | | ALL | |
| 222R | 22 | PB | AL | 0-0 | 21-51-12 | D05798P | | 41 | | D05782J | | 23 | | ALL | |
| 223B | 20 | PR | IW | 25-4 | 32-45-12 | D06802J | | 4 | | D05506P | | 51 | | 275-299 | |
| 223R | 20 | PR | IW | 0-0 | 32-45-12 | D06802J | | 3 | | D05506P | | 50 | | 275-299 | |
| 223Z | | | IW | 0-0 | 32-45-12 | D06802J | | 5 | | D05506P | | 29 | | 275-299 | |
| 224B | 20 | PR | IX | 25-4 | 32-45-12 | D06802J | | 7 | | D05506P | | 61 | | 275-299 | |
| 224R | 20 | PR | IX | 0-0 | 32-45-12 | D06802J | | 6 | | D05506P | | 60 | | 275-299 | |
| 224Z | | | IX | 0-0 | 32-45-12 | D06802J | | 8 | | D05506P | | 39 | | 275-299 | |
| 507 | 24 | PK | | 24-10 | 21-24-11 | D08068P | | 37 | | D04708P | | 8 | | 050-099, 150-199 | |
| 508 | 24 | PK | | 31-6 | 21-24-11 | D08068P | | 38 | | D05658P | | 40 | | 050-099, 150-199 | |
| 509 | 24 | PK | | 24-10 | 21-24-11 | D08068P | | 39 | | D04708P | | 28 | | 050-099, 150-199 | |
| 510 | 24 | PK | | 31-6 | 21-24-11 | D08068P | | 43 | | D05658P | | 41 | | 050-099, 150-199 | |
| 512 | 24 | PK | | 24-10 | 21-24-11 | D08068P | | 53 | | D04708P | | 6 | | 050-099, 150-199 | |
| 513 | 24 | PK | | 32-11 | 21-24-11 | D04708P | | 7 | | D05658P | | 43 | | 050-099, 150-199 | |
| 514 | 24 | PK | | 11-3 | 24-51-61 | D04662P | | 31 | | D05682P | | 2 | | ALL | |
| 523 | 22 | PA | | 32-11 | 28-31-11 | D04708P | | 13 | | D05658P | | 50 | | 050-099, 155-199, 276-299 | |
| 523 | 22 | PA | | 18-9 | SPARE | D04708P | | 13 | | D05506P | | 51 | | 150-154 | |
| 524 | 22 | PA | | 19-1 | SPARE | D05726P | | 60 | | D05506P | | 50 | | 050-099, 150-199 | |
| 528R | 22 | PH | | 19-1 | 26-18-21 | D05726P | | 61 | | D05506P | | 55 | | ALL | |
| 529 | 22 | PA | | 31-6 | 36-11-51 | D05658P | | 10 | | D08068P | | 44 | | 050-099, 150-155, 162-165, 275-276 | |
| 537R | 22 | PH | | 18-9 | 26-18-21 | D04708P | | 41 | | D05506P | | 41 | | ALL | |
| 538 | 22 | PA | | 24-10 | 21-24-11 | D08068P | | 54 | | D04708P | | 27 | | 050-099, 150-199 | |
| 542 | 24 | PK | | 17-4 | 21-58-14 | D05506P | | 9 | | D08068P | | 46 | | ALL | |
| 543 | 24 | PK | | 30-4 | 21-51-23 | D05798P | | 7 | | D08068P | | 45 | | ALL | |
| 544 | 24 | PK | | 31-6 | 28-22-12 | D05658P | | 4 | | D08068P | | 47 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0570

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-----|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0572 | 286T0572 | | | AIR COND RIGHT PACK ELEC HYD PUMP CONTROL & INDICATION (continued) | | | | | | | | | | | | | |
| 548 | 22 | | PA | 44-0 | 30-32-11 | D04708P | | 43 | | | | | SP02310 | | 9 | | ALL |
| 549 | 22 | | PA | 21-3 | 30-32-11 | D05798P | | 29 | | | | | SP02312 | | 9 | | ALL |
| 550 | 24 | | PK | 30-4 | 30-34-11 | D05798P | | 25 | | | | | D08068P | | 52 | | ALL |
| 556 | 22 | | PA | 16-7 | 36-11-61 | D04662P | | 53 | | | | | D05782J | | 9 | | ALL |
| 557 | 22 | | PA | 16-7 | 36-11-61 | D04662P | | 54 | | | | | D05782J | | 16 | | ALL |
| 559 | 24 | | PK | 15-5 | 21-51-23 | D06264J | | 1 | | | | | D05798P | | 14 | | ALL |
| 560 | 24 | | PK | 15-5 | 21-51-23 | D06264J | | 2 | | | | | D05798P | | 15 | | ALL |
| 561 | 24 | | PK | 15-5 | 21-51-23 | D06264J | | 3 | | | | | D05798P | | 16 | | ALL |
| 562 | 24 | | PK | 16-0 | 36-11-41 | D05506P | | 42 | | | | | D05798P | | 24 | | ALL |
| 563 | 24 | | PK | 16-0 | 36-11-41 | D05506P | | 43 | | | | | D05798P | | 23 | | ALL |
| 564 | 22 | | PQ | 10-2 | 32-41-11 | D05798P | | 35 | | | | | D05658P | | 34 | | ALL |
| 564Z | | | AM | 0-0 | 32-41-11 | D05798P | | DED | | | | | D05658P | | DED | | ALL |
| 565 | 24 | | PK | 30-4 | 30-31-11 | D05798P | | 2 | | | | | D08068P | | 51 | | ALL |
| 566 | 24 | | PK | 31-8 | 21-51-23 | D05798P | | 6 | | | | | D04708P | | 29 | | ALL |
| 567 | 24 | | PK | 31-8 | 21-51-23 | D05798P | | 21 | | | | | D04708P | | 30 | | ALL |
| 568 | 22 | | PA | 18-9 | SPARE | D04708P | | CAP | Y | | | | D05506P | | 29 | | 150-154 |
| 569 | 22 | | PA | 32-9 | 28-31-21 | D04708P | | 36 | | | | | D04662P | | 28 | | 050-099, 155-199, 276-299 |
| 569 | 22 | | PA | 18-9 | SPARE | D04708P | | 36 | | | | | D05506P | | 24 | | 150-154 |
| 570 | 22 | | PA | 18-9 | SPARE | D04708P | | 37 | | | | | D05506P | | 39 | | 150-199 |
| 571 | 22 | | PA | 18-9 | SPARE | D04708P | | 38 | | | | | D05506P | | 46 | | 150-199, 275-299 |
| 572 | 20 | | PA | 2-11 | 21-51-23 | D06264J | | 8 | | | | | GD00754 | | A.. | 2 | ALL |
| 576 | 22 | | PA | 10-2 | 32-42-11 | D05658P | | 7 | | | | | D05798P | | 42 | | ALL |
| 577 | 24 | | PK | 16-0 | 29-11-12 | D05506P | | 14 | | | | | D05798P | | 45 | | ALL |
| 578 | 24 | | PK | 16-0 | 29-11-22 | D05506P | | 15 | | | | | D05798P | | 46 | | ALL |
| 580 | 24 | | PK | 10-1 | SPARE | D05798P | | CAP | Y | | | | D04662P | | CAP | Y | 275-276 |
| 580 | 24 | | PK | 10-1 | SPARE | D05798P | | 44 | | | | | D04662P | | CAP | Y | 277-299 |
| 581 | 24 | | PK | 10-1 | SPARE | D05798P | | 43 | | | | | D04662P | | 12 | | 275-299 |
| 582 | 22 | | PA | 18-9 | 30-34-41 | D05506P | | 2 | | | | | D04708P | | 26 | | 150-199 |
| 583 | 24 | | PK | 16-7 | 36-11-61 | D05782J | | 24 | | | | | D04662P | | 13 | | ALL |
| 584 | 24 | | PK | 16-7 | 36-11-61 | D05782J | | 10 | | | | | D04662P | | 14 | | ALL |
| 585 | 24 | | PK | 17-3 | 24-22-11 | D05658P | | 13 | | | | | D05506P | | 13 | | ALL |
| 586 | 16 | | PA | 32-10 | 28-22-11 | D05910P | | 4 | | | | | D05930P | | 4 | | ALL |
| 587 | 16 | | PA | 32-10 | 28-22-11 | D05910P | | 5 | | | | | D05930P | | 5 | | ALL |
| 588 | 16 | | PA | 32-10 | 28-22-11 | D05910P | | 6 | | | | | D05930P | | 6 | | ALL |
| 589 | 16 | | PA | 32-10 | 28-22-11 | D05910P | | 7 | | | | | D05930P | | 7 | | ALL |
| 590 | 16 | | PA | 32-10 | 28-22-11 | D05910P | | 8 | | | | | D05930P | | 8 | | ALL |
| 591 | 16 | | PA | 32-10 | 28-22-11 | D05910P | | 9 | | | | | D05930P | | 9 | | ALL |
| 592 | 24 | | PK | 31-5 | SPARE | D08068P | | 48 | | | | | D04662P | | 22 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0570

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0572 | 286T0572 | | | AIR COND RIGHT PACK ELEC HYD PUMP CONTROL & INDICATION (continued) | | | | | | | | | | | |
| 592 | 24 | | PK | | 31-5 | 21-58-16 | D08068P | | | | D04662P | 22 | | | 150-199, 275-299 |
| 593 | 24 | | PK | | 31-5 | 21-26-11 | D08068P | | | | D04662P | 23 | | | ALL |
| 594 | 24 | | PK | | 31-5 | SPARE | D08068P | | | | D04662P | 24 | | | 050-099 |
| 594 | 24 | | PK | | 31-5 | 21-58-16 | D08068P | | | | D04662P | 24 | | | 150-199, 275-299 |
| 595 | 24 | | PK | | 17-1 | 21-58-16 | D05506P | | | | D04662P | 25 | | | ALL |
| 598 | 24 | | PK | | 17-1 | 36-11-41 | D05506P | | | 6 | D04662P | 34 | | | ALL |
| 599 | 24 | | PK | | 17-1 | 36-11-41 | D05506P | | | 5 | D04662P | 32 | | | ALL |
| 600 | 24 | | PK | | 31-5 | 36-11-41 | D08068P | | | 30 | D04662P | 33 | | | ALL |
| 601 | 22 | | PA | | 30-4 | 36-11-51 | D08068P | | | 17 | D05798P | 48 | | | ALL |
| 602 | 22 | | PA | | 32-9 | 29-21-32 | D04708P | | | 39 | D04662P | 29 | | | ALL |
| 603 | 22 | | PA | | 32-9 | 29-21-32 | D04708P | | | 40 | D04662P | 30 | | | ALL |
| 604 | 24 | | PK | | 32-9 | 21-45-21 | D04708P | | | 55 | D04662P | 50 | | | ALL |
| 605 | 22 | | PA | | 32-9 | 21-45-21 | D04708P | | | 56 | D04662P | 51 | | | 050-099, 150-156, 162-166, 275-276 |
| 605 | 20 | | PA | | 32-9 | 21-45-21 | D04708P | | | 56 | D04662P | 51 | | | 157, 167-199, 277-299 |
| 606 | 22 | | PA | | 32-9 | 21-45-21 | D04708P | | | 57 | D04662P | 52 | | | 050-099, 150-156, 162-166, 275-276 |
| 606 | 20 | | PA | | 32-9 | 21-45-21 | D04708P | | | 57 | D04662P | 52 | | | 157, 167-199, 277-299 |
| 607 | 24 | | PK | | 17-1 | 21-45-21 | D05506P | | | 37 | D04662P | 37 | | | ALL |
| 628 | 24 | | PK | | 31-5 | 36-11-61 | D08068P | | | 35 | D04662P | 35 | | | 050-099, 150-156, 162-166, 275-276 |
| 637 | 24 | | PK | | 32-9 | 21-58-11 | D04708P | | | 42 | D04662P | 26 | | | ALL |
| 638 | 24 | | PK | | 32-9 | 21-58-11 | D04708P | | | 58 | D04662P | 27 | | | ALL |
| 640 | 24 | | PK | | 17-3 | 21-61-21 | D05506P | | | 10 | D05658P | 35 | | | ALL |
| 641 | 24 | | PK | | 17-3 | 21-61-21 | D05506P | | | 21 | D05658P | 36 | | | ALL |
| 642 | 24 | | PK | | 17-3 | 21-61-41 | D05506P | | | 36 | D05658P | 14 | | | ALL |
| 643 | 24 | | PK | | 17-3 | 21-61-41 | D05506P | | | 44 | D05658P | 15 | | | ALL |
| 644 | 24 | | PK | | 32-11 | 21-61-61 | D04708P | | | 48 | D05658P | 9 | | | ALL |
| 645 | 22 | | PA | | 17-3 | 21-28-11 | D05506P | | | 12 | D05658P | 44 | | | 050-099, 150-199, 275-276 |
| 646 | 22 | | PA | | 17-3 | 21-28-11 | D05506P | | | 22 | D05658P | 45 | | | 050-099, 150-199, 275-276 |
| 647 | 24 | | PK | | 17-3 | 21-28-11 | D05506P | | | 56 | D05658P | 46 | | | ALL |
| 648 | 24 | | PK | | 17-3 | 21-43-11 | D05506P | | | 57 | D05658P | 47 | | | ALL |
| 649 | 24 | | PK | | 17-3 | 21-43-11 | D05506P | | | 58 | D05658P | 48 | | | ALL |
| 650 | 24 | | PK | | 17-3 | 21-43-11 | D05506P | | | 59 | D05658P | 49 | | | ALL |
| 660 | 24 | | PK | | 32-9 | 21-45-22 | D04708P | | | 35 | D04662P | 38 | | | ALL |
| 663 | 22 | | PA | | 39-3 | 32-45-11 | D06286P | | | 4 | D06802J | 1 | | | 275-299 |
| 664 | 22 | | PA | | 25-4 | 32-45-11 | D05506P | | | 20 | D06802J | 2 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0570

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0572 | 286T0572 | | | AIR COND RIGHT PACK ELEC HYD PUMP CONTROL & INDICATION (continued) | | | | | | | | | | | | |
| 665 | 22 | | PA | 16-11 | 32-45-11 | D05506P | 24 | | | | D06286P | 5 | | | | 275-299 |
| 666 | 18 | | PA | 33-2 | SPARE | D05726P | 17 | DL | | | D04662P | 36 | DL | | | 050-099, 155, 162-165, 276 |
| 666 | 18 | | PA | 33-2 | SPARE | D05726P | 17 | DL | | | D04662P | CAP | Y | | | 156-157, 166-199, 277-299 |
| 680 | 20 | | PA | 32-11 | 28-31-11 | D04708P | 31 | | | | D05658P | 52 | | | | 050-099, 155-199, 276-299 |
| 681 | 22 | | PQ | D1 | 32-11 | 28-31-11 | D04708P | 32 | | | D05658P | 53 | | | | 050-099, 155-199, 276-299 |
| 681Z | | | | D1 | 0-0 | 28-31-11 | D04708P | DED | | | D05658P | DED | | | | 050-099, 155-199, 276-299 |
| 682 | 20 | | PA | 33-3 | 24-51-72 | D05658P | 42 | | | | D05726P | 47 | | | | 050-099, 162-164, 276 |
| 682 | 20 | | PA | 33-3 | SPARE | D05658P | 42 | | | | D05726P | 47 | | | | 155-157, 165-199, 277-299 |
| 683 | 24 | | PK | 17-3 | 30-21-11 | D05658P | 2 | | | | D05506P | 60 | | | | 050-099, 150-199 |
| 688 | 18 | | PA | 25-2 | 36-11-51 | D05726P | 18 | DL | | | D08068P | 44 | DL | | | 156-157, 166-199, 277-299 |
| 689 | 22 | | PA | 31-6 | 36-11-51 | D05658P | 10 | | | | D08068P | 49 | | | | 156, 166 |
| 690 | 22 | | PA | 33-1 | 21-66-11 | D05930P | 1 | | | | D05726P | 11 | | | | 050-099, 162-199 |
| 691 | 24 | | PK | 15-7 | 36-11-51 | D05798P | 44 | | | | D08092J | 36 | | | | 050-099, 150-154, 163-165, 275-276 |
| 691 | 24 | | PK | 15-7 | 36-11-51 | D05798P | 18 | | | | D08092J | 36 | | | | 156-162, 166-199, 277-299 |
| 692 | 22 | | PA | 16-8 | 36-11-61 | D08092J | 5 | | | | D04662P | 11 | | | | 050-099, 150-155, 163-165, 275-276 |
| 692 | 22 | | PA | 16-7 | 36-11-61 | D05782J | 5 | | | | D04662P | 11 | | | | 156-157, 166-199, 277-299 |
| 692 | 22 | | PA | 16-7 | 36-11-61 | D05782J | 14 | | | | D04662P | 11 | | | | 162 |
| 693 | 22 | | PA | 16-8 | 36-11-61 | D08092J | 7 | | | | D04662P | 10 | | | | 050-099, 150-155, 163-165, 275-276 |
| 693 | 22 | | PA | 16-7 | 36-11-61 | D05782J | 1 | | | | D04662P | 10 | | | | 156-162, 166-199, 277-299 |
| 694 | 22 | | PA | 16-8 | 36-11-61 | D08092J | 4 | | | | D04662P | 8 | | | | 050-099, 150-155, 163-165, 275-276 |
| 694 | 22 | | PA | 16-7 | 36-11-61 | D05782J | 4 | | | | D04662P | 8 | | | | 156-162, 166-199, 277-299 |
| 695 | 20 | | PA | 16-6 | 36-23-11 | D06286P | 6 | | | | D08092J | 25 | | | | ALL |
| 696 | 20 | | PA | 16-6 | 36-23-11 | D06286P | 7 | | | | D08092J | 26 | | | | ALL |
| 697 | 20 | | PA | 16-6 | 36-23-11 | D06286P | 8 | | | | D08092J | 31 | | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0570

Page 8

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0572 | 286T0572 | | | AIR COND RIGHT PACK ELEC HYD PUMP CONTROL & INDICATION (continued) | | | | | | | | | | | |
| 70C | 20 | | PA | | 18-9 | 29-11-14 | D04708P | | 51 | | D05506P | | 23 | | ALL |
| 70D | 20 | | PA | | 18-9 | 29-11-14 | D04708P | | 54 | | D05506P | | 45 | | ALL |
| 710 | 22 | | PA | | 32-9 | 30-21-11 | D04708P | | 46 | | D05930P | | 2 | | 050-099, 150-199 |
| 759 | 24 | | PK | | 25-0 | 21-45-21 | D05506P | | 2 | | D05658P | | 40 | | 275-299 |
| 760 | 24 | | PK | | 25-0 | 21-45-21 | D05506P | | 40 | | D05658P | | 41 | | 275-299 |
| 801 | 16 | | PA | | 20-3 | SPARE | D05910P | | 10 | | D08092J | | 40 | FM | 050-099, 155-199, 276-299 |
| 801 | 16 | | PA | | 20-3 | 36-11-51 | D05910P | | 10 | | D08092J | | 40 | FM | 150-154, 275 |
| 802 | 16 | | PA | | 32-11 | SPARE | D05910P | | 11 | | D04662P | | 55 | FL | ALL |
| 803 | 16 | | PA | | 18-10 | SPARE | D05910P | | 12 | | D05506P | | 52 | FM | ALL |
| 804 | 22 | | PA | | 20-1 | SPARE | D04708P | | 60 | | D05782J | | 17 | | ALL |
| 805 | 20 | | PA | | 31-8 | 30-32-11 | D04708P | | 61 | | D05798P | | 50 | | ALL |
| W0575 | 286T0575 | | | STAB. POS XMTR & STAB. TRIM CONT L | | | | | | | | | | | |
| 001 | 20 | | UA | | 29-0 | 27-41-11 | D04531J | | 6 | | D02211 | | 3 | | 050-099 |
| 001 | 20 | | UA | | 28-0 | 27-41-11 | D04531J | | 6 | | D00229 | | 3 | | 150-154 |
| 001 | 20 | | UA | | 28-1 | 27-41-11 | D04531J | | 6 | | D02211 | | 3 | | 155-199, 275-299 |
| 002 | 20 | | UA | | 29-0 | 27-41-11 | D04531J | | 7 | | D02211 | | 2 | | 050-099 |
| 002 | 20 | | UA | | 28-0 | 27-41-11 | D04531J | | 7 | | D00229 | | 2 | | 150-154 |
| 002 | 20 | | UA | | 28-1 | 27-41-11 | D04531J | | 7 | | D02211 | | 2 | | 155-199, 275-299 |
| 003 | 18 | | UA | | 5-0 | 27-41-11 | GD00137 | | D.. | N | D02211 | | 1 | DK | 050-099 |
| 003 | 18 | | UA | | 5-0 | 27-41-11 | GD00137 | | D.. | N | D00229 | | 1 | DK | 150-154 |
| 003 | 18 | | UA | | 4-0 | 27-41-11 | GD00137 | | D.. | N | D02211 | | 1 | DK | 155-199, 275-299 |
| 004Y | 20 | | XP | | 18-0 | 27-41-11 | D02209 | | 2 | | D00225 | | 17 | | 050-099 |
| 004Y | 20 | | XP | | 19-0 | 27-41-11 | D00223 | | 13 | | D00225 | | 17 | | 150-154 |
| 004Y | 20 | | XP | | 17-8 | 27-41-11 | D02209 | | 2 | | D00225 | | 17 | | 155-199, 275-299 |
| 005Y | 18 | | XP | | 5-0 | 27-41-11 | D02209 | | 1 | | GD00137 | | D.. | N | 050-099 |
| 005Y | 18 | | XP | | 5-0 | 27-41-11 | D00223 | | 12 | DK | GD00137 | | D.. | N | 150-154 |
| 005Y | 18 | | XP | | 4-0 | 27-41-11 | D02209 | | 1 | | GD00137 | | D.. | N | 155-199, 275-299 |
| 006Y | 20 | | XP | | 18-0 | 27-41-11 | D02209 | | 6 | | D00225 | | 21 | | 050-099 |
| 006Y | 20 | | XP | | 19-0 | 27-41-11 | D00223 | | 8 | | D00225 | | 21 | | 150-154 |
| 006Y | 20 | | XP | | 17-8 | 27-41-11 | D02209 | | 6 | | D00225 | | 21 | | 155-199, 275-299 |
| 007Y | 18 | | XP | | 5-0 | 27-41-11 | D02209 | | 5 | | GD00137 | | D.. | N | 050-099 |
| 007Y | 18 | | XP | | 5-0 | 27-41-11 | D00223 | | 7 | DK | GD00137 | | D.. | N | 150-154 |
| 007Y | 18 | | XP | | 4-0 | 27-41-11 | D02209 | | 5 | | GD00137 | | D.. | N | 155-199, 275-299 |
| 009 | 18 | | UA | | 5-0 | 27-41-11 | D02211 | | 8 | DK | GD00671 | | S.. | N | 050-099 |
| 009 | 18 | | UA | | 5-0 | 27-41-11 | D00229 | | 8 | DK | GD00671 | | S.. | N | 150-154 |
| 009 | 18 | | UA | | 4-0 | 27-41-11 | D02211 | | 8 | DK | GD00671 | | S.. | N | 155-199, 275-299 |
| 010Y | 20 | | XP | | 32-0 | 27-41-11 | D00225 | | 20 | | D04531J | | 10 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0570

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0575 | 286T0575 | | | STAB. POS XMTR & STAB. TRIM CONT L (continued) | | | | | | | | | | | | | |
| 010Y | 20 | | XP | 33-0 | 27-41-11 | D00225 | | 20 | | | | | D04531J | 10 | | | 150-154 |
| 010Y | 20 | | XP | 31-7 | 27-41-11 | D00225 | | 20 | | | | | D04531J | 10 | | | 155-199, 275-299 |
| 011Y | 20 | | XP | 32-0 | 27-41-11 | D00225 | | 19 | | | | | D04531J | 8 | | | 050-099 |
| 011Y | 20 | | XP | 33-0 | 27-41-11 | D00225 | | 16 | | | | | D04531J | 8 | | | 150-154 |
| 011Y | 20 | | XP | 31-7 | 27-41-11 | D00225 | | 16 | | | | | D04531J | 8 | | | 155-199, 275-299 |
| 012Y | 20 | | XP | 32-0 | 27-41-11 | D00225 | | 16 | | | | | D04531J | 9 | | | 050-099 |
| 013Y | 18 | | XP | 5-0 | 27-41-11 | D02209 | | 10 | | | | | GD00671 | S.. | N | | 050-099 |
| 013Y | 18 | | XP | 5-0 | 27-41-11 | D00223 | | 6 | DK | | | | GD00671 | S.. | N | | 150-154 |
| 013Y | 18 | | XP | 4-0 | 27-41-11 | D02209 | | 10 | | | | | GD00671 | S.. | N | | 155-199, 275-299 |
| 015 | 18 | | UA | 4-0 | 27-48-11 | D00225 | | 10 | DK | | | | GD00537 | A.. | N | | 050-099 |
| 015 | 18 | | UA | 5-0 | 27-48-11 | D00225 | | 10 | DK | | | | GD00537 | A.. | N | | 150-154 |
| 015 | 18 | | UA | 3-2 | 27-48-11 | D00225 | | 10 | DK | | | | GD00537 | A.. | N | | 155-156, 162-166, 275-276 |
| 016 | 18 | | UA | 4-0 | 27-48-11 | D00225 | | 12 | DK | | | | GD00537 | A.. | N | | 050-099 |
| 016 | 18 | | UA | 5-0 | 27-48-11 | D00225 | | 12 | DK | | | | GD00537 | A.. | N | | 150-154 |
| 016 | 18 | | UA | 3-2 | 27-48-11 | D00225 | | 12 | DK | | | | GD00537 | A.. | N | | 155-199, 275-299 |
| 017 | 20 | | UA | 32-0 | 27-48-11 | D00225 | | 11 | | | | | D04531J | 1 | | | 050-099 |
| 017 | 20 | | UA | 33-0 | 27-48-11 | D00225 | | 11 | | | | | D04531J | 1 | | | 150-154 |
| 017 | 20 | | UA | 31-7 | 27-48-11 | D00225 | | 11 | | | | | D04531J | 1 | | | 157-164, 167-199, 275-299 |
| 018 | 20 | | UA | 33-0 | 27-48-11 | D00225 | | 9 | | | | | D04533J | 2 | | | 050-099 |
| 018 | 20 | | UA | 33-0 | 27-48-11 | D00225 | | 9 | | | | | D04531J | 2 | | | 150-154 |
| 018 | 20 | | UA | 31-7 | 27-48-11 | D00225 | | 9 | | | | | D04531J | 2 | | | 162-164, 275-276 |
| 019 | 20 | | UA | 33-0 | 27-48-11 | D00225 | | 8 | | | | | D04533J | 3 | | | 050-099 |
| 019 | 20 | | UA | 33-0 | 27-48-11 | D00225 | | 8 | | | | | D04531J | 3 | | | 150-154 |
| 019 | 20 | | UA | 31-7 | 27-48-11 | D00225 | | 8 | | | | | D04531J | 3 | | | 162-164, 275-276 |
| 020 | 18 | | UA | 4-0 | 27-58-21 | D00225 | | 31 | DK | | | | GD00575 | S.. | N | | 050-099 |
| 020 | 18 | | UA | 5-0 | 27-58-21 | D00225 | | 31 | DK | | | | GD00575 | S.. | N | | 150-154 |
| 020 | 18 | | UA | 3-4 | 27-58-21 | D00225 | | 31 | DK | | | | GD00575 | S.. | N | | 155-199, 275-299 |
| 021Y | 20 | | XP | 32-0 | 27-41-11 | SP00391 | | 9 | | | | | D00225 | 18 | | | 050-099, 150-154 |
| 021Y | 20 | | XP | 31-10 | 27-41-11 | SP00391 | | 9 | | | | | D00225 | 18 | | | 155-199, 275-299 |
| 022Y | 20 | | XP | 53-0 | 27-41-31 | D02209 | | 8 | | | | | D06029J | 1 | | | 050-099 |
| 022Y | 20 | | XP | 52-4 | 27-41-31 | D02209 | | 8 | | | | | D06029J | 1 | | | 155-199, 275-299 |
| 023Y | 20 | | XP | 53-0 | 27-41-31 | D02209 | | 4 | | | | | D06029J | 2 | | | 050-099 |
| 023Y | 20 | | XP | 52-4 | 27-41-31 | D02209 | | 4 | | | | | D06029J | 2 | | | 155-199, 275-299 |
| 024Y | 18 | | XP | 5-0 | 27-41-31 | D02209 | | 3 | | | | | GD00761 | D.. | N | | 050-099 |
| 024Y | 18 | | XP | 4-0 | 27-41-31 | D02209 | | 3 | | | | | GD00761 | D.. | N | | 155-199, 275-299 |
| 025Y | 18 | | XP | 6-0 | 27-41-31 | D02209 | | 7 | | | | | GD00761 | D.. | N | | 050-099 |
| 025Y | 18 | | XP | 4-0 | 27-41-31 | D02209 | | 7 | | | | | GD00761 | D.. | N | | 155-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0570

Page 10

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0575 | 286T0575 | | | STAB. POS XMTR & STAB. TRIM CONT L (continued) | | | | | | | | | | | |
| 201B | 20 | UB | IA | 32-0 | 27-58-21 | D00225 | | 1 | | D04531J | | 11 | | 050-099 | |
| 201B | 20 | UB | IA | 33-0 | 27-58-21 | D00225 | | 1 | | D04531J | | 11 | | 150-154 | |
| 201B | 20 | UB | IA | 31-7 | 27-58-21 | D00225 | | 1 | | D04531J | | 11 | | 155-199, 275-299 | |
| 201R | 20 | UB | IA | 0-0 | 27-58-21 | D00225 | | 7 | | D04531J | | 12 | | ALL | |
| 301B | 20 | UC | MA | 32-0 | 27-58-21 | D00225 | | 2 | | D04531J | | 13 | | 050-099 | |
| 301B | 20 | UC | MA | 33-0 | 27-58-21 | D00225 | | 2 | | D04531J | | 13 | | 150-154 | |
| 301B | 20 | UC | MA | 31-7 | 27-58-21 | D00225 | | 2 | | D04531J | | 13 | | 155-199, 275-299 | |
| 301R | 20 | UC | MA | 0-0 | 27-58-21 | D00225 | | 3 | | D04531J | | 14 | | ALL | |
| 301Y | 20 | UC | MA | 0-0 | 27-58-21 | D00225 | | 4 | | D04531J | | 15 | | ALL | |
| 302B | 20 | UC | MB | 31-7 | 27-48-11 | D00225 | | 9 | | D04531J | | 2 | | 155-157, 165-199, 277-299 | |
| 302R | 20 | UC | MB | 0-0 | 27-48-11 | D00225 | | 8 | | D04531J | | 3 | | 155-157, 165-199, 277-299 | |
| 302Y | 20 | UC | MB | 0-0 | 27-48-11 | D00225 | | 11 | | D04531J | | 1 | | 155-156, 165-166 | |
| 302Y | 20 | UC | MB | 0-0 | 27-48-11 | D00225 | | 10 | | D04531J | | 4 | | 157, 167-199, 277-299 | |
| W0578 | 286T0578 | | | AIR COND,RECIRC FANS,CARGO HT & EQUIP COOLING | | | | | | | | | | | |
| 002 | 12 | PA | | 50-1 | 21-25-11 | D04920P | | 2 | | D00448 | | 2 | | 050-099 | |
| 002 | 12 | PA | | 62-6 | 21-25-11 | D04920P | | 2 | | D00448 | | 2 | | 150-199, 275-299 | |
| 003 | 12 | PA | | 50-1 | 21-25-11 | D04920P | | 3 | | D00448 | | 3 | | 050-099 | |
| 003 | 12 | PA | | 62-6 | 21-25-11 | D04920P | | 3 | | D00448 | | 3 | | 150-199, 275-299 | |
| 004 | 12 | PA | | 50-1 | 21-25-11 | D04920P | | 4 | | D00448 | | 4 | | 050-099 | |
| 004 | 12 | PA | | 62-6 | 21-25-11 | D04920P | | 4 | | D00448 | | 4 | | 150-199, 275-299 | |
| 005 | 18 | PA | | 50-1 | 21-25-11 | D04920P | | 1 | | D00448 | | 5 | | 050-099 | |
| 005 | 18 | PA | | 62-6 | 21-25-11 | D04920P | | 1 | | D00448 | | 5 | | 150-199, 275-299 | |
| 006 | 18 | PA | | 2-9 | 21-25-11 | D00448 | | 6 | | GD00750 | D.. | E | | 050-099 | |
| 006 | 18 | PA | | 4-4 | 21-25-11 | D00448 | | 6 | | GD00750 | D.. | E | | 150-199, 275-299 | |
| 007 | 12 | PA | | 5-0 | 21-25-11 | D00448 | | 7 | | GD00752 | S.. | E | | ALL | |
| 008 | 24 | PK | | 45-3 | 21-43-11 | D04918P | | 27 | | D02768 | | 2 | | 050-099 | |
| 008 | 24 | PK | | 44-11 | 21-43-11 | D04918P | | 27 | | D02768 | | 2 | | 150-199, 275-299 | |
| 011 | 24 | PK | | 45-3 | 21-43-11 | D04918P | | 29 | | D02768 | | 1 | | 050-099 | |
| 011 | 24 | PK | | 44-11 | 21-43-11 | D04918P | | 29 | | D02768 | | 1 | | 150-199, 275-299 | |
| 013 | 24 | PK | | 47-2 | 21-53-11 | D04918P | | 5 | | D08044J | | 1 | | 050-099 | |
| 013 | 24 | PK | | 58-1 | 21-53-11 | D04918P | | 5 | | D08044J | | 1 | | 150-199, 275-299 | |
| 014 | 24 | PK | | 47-2 | 21-53-11 | D04918P | | 22 | | D08044J | | 2 | | 050-099 | |
| 014 | 24 | PK | | 58-1 | 21-53-11 | D04918P | | 22 | | D08044J | | 2 | | 150-199, 275-299 | |
| 015 | 24 | PK | | 47-2 | 21-53-11 | D04918P | | 7 | | D08044J | | 3 | | 050-099 | |
| 015 | 24 | PK | | 58-1 | 21-53-11 | D04918P | | 7 | | D08044J | | 3 | | 150-199, 275-299 | |
| 016 | 24 | PK | | 47-2 | 21-53-11 | D04918P | | 26 | | D08044J | | 8 | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0570

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-----|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W0578 | 286T0578 | | | AIR COND,RECIRC FANS,CARGO HT & EQUIP COOLING (continued) | | | | | | | | | | | | | | |
| 016 | 24 | | PK | 58-1 | 21-53-11 | D04918P | | 26 | | | | | D08044J | | 8 | | | 150-199, 275-299 |
| 017 | 24 | | PK | 47-2 | 21-53-11 | D04918P | | 9 | | | | | D08044J | | 5 | | | 050-099 |
| 017 | 24 | | PK | 58-1 | 21-53-11 | D04918P | | 9 | | | | | D08044J | | 5 | | | 150-199, 275-299 |
| 018 | 24 | | PK | 47-2 | 21-53-11 | D04918P | | 32 | | | | | D08044J | | 6 | | | 050-099 |
| 018 | 24 | | PK | 58-1 | 21-53-11 | D04918P | | 32 | | | | | D08044J | | 6 | | | 150-199, 275-299 |
| 019 | 22 | | PA | 110-7 | 21-44-11 | D04918P | | 14 | | | | | D00646 | | 5 | | | 050-099 |
| 019 | 22 | | PA | 131-7 | 21-44-11 | D04918P | | 14 | | | | | D00646 | | 5 | | | 150-199, 275-299 |
| 020 | 24 | | PK | 110-7 | 21-44-11 | D04918P | | 15 | | | | | D00646 | | 2 | | | 050-099 |
| 020 | 24 | | PK | 131-7 | 21-44-11 | D04918P | | 15 | | | | | D00646 | | 2 | | | 150-199, 275-299 |
| 021 | 24 | | PK | 110-7 | 21-44-11 | D04918P | | 16 | | | | | D00646 | | 1 | | | 050-099 |
| 021 | 24 | | PK | 131-7 | 21-44-11 | D04918P | | 16 | | | | | D00646 | | 1 | | | 150-199, 275-299 |
| 022 | 24 | | PK | 100-5 | 21-44-11 | D04918P | | 17 | | | | | D05950J | | 1 | | | 050-099 |
| 022 | 24 | | PK | 122-6 | 21-44-11 | D04918P | | 17 | | | | | D05950J | | 1 | | | 150-199, 275-299 |
| 024 | 20 | | PA | 4-0 | 21-44-11 | D00646 | | 3 | | | | | GD01140 | A.. | | E | | 050-099 |
| 024 | 20 | | PA | 4-5 | 21-44-11 | D00646 | | 3 | | | | | GD01140 | A.. | | E | | 150-199, 275-299 |
| 025 | 22 | | PA | 4-7 | 21-44-11 | D00646 | | 4 | | | | | SP00460 | | | S | | ALL |
| 026 | 18 | | PA | 47-0 | 33-31-21 | D08044J | | 10 | | | | | D04920P | | 11 | | | 050-099 |
| 026 | 18 | | PA | 58-1 | 33-31-21 | D08044J | | 10 | | | | | D04920P | | 11 | | | 150-199, 275-299 |
| 027 | 18 | | PA | 23-2 | 33-31-21 | D08044J | | 4 | | | | | D04620J | | 4 | | | 050-099 |
| 027 | 18 | | PA | 24-0 | 33-31-21 | D08044J | | 4 | | | | | D04620J | | 4 | | | 150-199, 275-299 |
| 028 | 14 | | PA | 124-3 | 21-26-11 | D04920P | | 8 | | | | | D06314P | | 14 | | | 050-099 |
| 028 | 14 | | PA | 145-9 | 21-26-11 | D04920P | | 8 | | | | | D06314P | | 14 | | | 150-199, 275-299 |
| 029 | 14 | | PA | 124-3 | 21-26-11 | D04920P | | 9 | | | | | D06314P | | 16 | | | 050-099 |
| 029 | 14 | | PA | 145-9 | 21-26-11 | D04920P | | 9 | | | | | D06314P | | 16 | | | 150-199, 275-299 |
| 030 | 14 | | PA | 124-3 | 21-26-11 | D04920P | | 10 | | | | | D06314P | | 18 | | | 050-099 |
| 030 | 14 | | PA | 145-9 | 21-26-11 | D04920P | | 10 | | | | | D06314P | | 18 | | | 150-199, 275-299 |
| 031 | 24 | | PV | N | 124-5 | 21-26-11 | D04918P | | 18 | | | | D06314P | | 1 | | | 050-099 |
| 031 | 24 | | PV | N | 145-10 | 21-26-11 | D04918P | | 18 | | | | D06314P | | 1 | | | 150-199, 275-299 |
| 031Z | | | | N | 0-0 | 21-26-11 | D04918P | | DED | | | | D06314P | | DED | | | ALL |
| 039 | 20 | | PA | | 124-5 | 21-31-11 | D06314P | | 5 | | | | D04918P | | 19 | | | 050-099 |
| 039 | 20 | | PA | | 145-10 | 21-31-11 | D06314P | | 5 | | | | D04918P | | 19 | | | 150-199, 275-299 |
| 041 | 18 | | PA | | 124-3 | 38-32-14 | D05952P | | 9 | DL | | | D06314P | | 12 | DK | | 050-099 |
| 041 | 18 | | PA | | 145-9 | 38-32-14 | D05952P | | 9 | DL | | | D06314P | | 12 | DK | | 150-154, 275-276 |
| 042 | 18 | | PA | | 124-3 | 38-32-14 | D05952P | | 10 | DL | | | D06314P | | 13 | DK | | 050-099 |
| 042 | 18 | | PA | | 145-9 | 38-32-14 | D05952P | | 10 | DL | | | D06314P | | 13 | DK | | 150-199, 275-299 |
| 043 | 22 | | PA | | 110-7 | 21-44-21 | D04918P | | 23 | | | | D00576 | | 2 | | | 050-099 |
| 043 | 22 | | PA | | 131-8 | 21-44-21 | D04918P | | 23 | | | | D00576 | | 2 | | | 150-199, 275-299 |
| 044 | 22 | | PA | | 110-7 | 21-44-21 | D04918P | | 24 | | | | D00576 | | 1 | | | 050-099 |
| 044 | 22 | | PA | | 131-8 | 21-44-21 | D04918P | | 24 | | | | D00576 | | 1 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0570

Page 12

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0578 | 286T0578 | | | AIR COND,RECIRC FANS,CARGO HT & EQUIP COOLING (continued) | | | | | | | | | | | |
| 045 | 22 | | PA | | 110-7 | 21-44-21 | D04918P | | | | D00576 | | | | 050-099 |
| 045 | 22 | | PA | | 131-8 | 21-44-21 | D04918P | | | | D00576 | | | | 150-199, 275-299 |
| 046 | 20 | | PA | | 4-0 | 21-44-21 | D00576 | | | 3 | GD01140 | A.. | E | | 050-099 |
| 046 | 20 | | PA | | 4-6 | 21-44-21 | D00576 | | | 3 | GD01140 | A.. | E | | 150-199, 275-299 |
| 047 | 22 | | PA | | 4-7 | 21-44-21 | D00576 | | | 4 | SP01464 | | S | | ALL |
| 053 | 22 | | PA | | 124-3 | 38-32-11 | D06314P | | | 11 | D05952P | | | 6 | 050-099 |
| 053 | 20 | | PA | | 145-9 | 38-32-11 | D06314P | | | 11 | D05952P | | | 6 | 150-156, 162-164 |
| 053 | 18 | | PA | | 145-9 | 38-32-11 | D06314P | | DK | 11 | D05952P | | DL | 6 | 157, 165-199, 277-299 |
| 053 | 22 | | PA | | 145-9 | 38-32-11 | D06314P | | | 11 | D05952P | | | 6 | 275-276 |
| 054 | 22 | | PA | | 124-3 | 38-32-11 | D06314P | | | 10 | D05952P | | | 1 | 050-099 |
| 054 | 20 | | PA | | 145-9 | 38-32-11 | D06314P | | | 10 | D05952P | | | 1 | 150-156, 162-165 |
| 054 | 18 | | PA | | 17-5 | 38-32-11 | D06314P | | DK | 10 | SP03988 | | 9 | | 157, 277-299 |
| 054 | 18 | | PA | | 17-5 | 38-32-11 | D06314P | | DK | 10 | SP03988 | | S | | 166-199 |
| 054 | 22 | | PA | | 145-9 | 38-32-11 | D06314P | | | 10 | D05952P | | | 1 | 275-276 |
| 056 | 12 | | PA | | 124-3 | 38-32-11 | D05952P | | | 20 | D06314P | | | 24 | 050-099 |
| 056 | 12 | | PA | | 145-9 | 38-32-11 | D05952P | | | 20 | D06314P | | | 24 | 150-199, 275-299 |
| 057 | 12 | | PA | | 124-3 | 38-32-11 | D05952P | | | 22 | D06314P | | | 22 | 050-099 |
| 057 | 12 | | PA | | 145-9 | 38-32-11 | D05952P | | | 22 | D06314P | | | 22 | 150-199, 275-299 |
| 058 | 12 | | PA | | 124-3 | 38-32-11 | D05952P | | | 24 | D06314P | | | 20 | 050-099 |
| 058 | 12 | | PA | | 145-9 | 38-32-11 | D05952P | | | 24 | D06314P | | | 20 | 150-199, 275-299 |
| 059 | 22 | | PA | | 124-3 | 38-32-11 | D05952P | | | 2 | D06314P | | | 9 | 050-099 |
| 059 | 20 | | PA | | 145-9 | 38-32-11 | D05952P | | | 2 | D06314P | | | 9 | 150-199 |
| 059 | 22 | | PA | | 145-9 | 38-32-11 | D05952P | | | 2 | D06314P | | | 9 | 275-299 |
| 060 | 22 | | PA | | 17-7 | 38-32-11 | SP01628 | | | 9 | D06314P | | | 8 | 050-099 |
| 060 | 20 | | PA | | 17-5 | 38-32-11 | SP01628 | | | 9 | D06314P | | | 8 | 150-199 |
| 060 | 22 | | PA | | 17-5 | 38-32-12 | SP01628 | | | 9 | D06314P | | | 8 | 275-276 |
| 060 | 22 | | PA | | 17-5 | 38-32-11 | SP01628 | | | 9 | D06314P | | | 8 | 277-299 |
| 067 | 20 | | PA | | 124-3 | 38-32-11 | D05952P | | | 11 | D06314P | | | 15 | 050-099 |
| 067 | 20 | | PA | | 145-9 | 38-32-11 | D05952P | | | 11 | D06314P | | | 15 | 155-199, 277-299 |
| 067 | 20 | | PA | | 145-9 | SPARE | D05952P | | | 11 | D06314P | | | 15 | 276 |
| 068 | 20 | | PA | | 124-3 | SPARE | D05952P | | | 25 | D06314P | | | 25 | 050-099 |
| 068 | 20 | | PA | | 145-9 | SPARE | D05952P | | | 25 | D06314P | | | 25 | 155, 162-165 |
| 069 | 20 | | PA | | 124-3 | SPARE | D05952P | | | 23 | D06314P | | | 23 | 050-099 |
| 069 | 20 | | PA | | 145-9 | SPARE | D05952P | | | 23 | D06314P | | | 23 | 155, 162-165 |
| 070 | 10 | | PA | | 73-5 | 28-31-21 | D04918P | | EO | 6 | D05558J | | EO | 4 | 050-099 |
| 070 | 10 | | PA | | 86-3 | 28-31-21 | D04918P | | EO | 6 | D05558J | | EO | 4 | 155-199, 276-299 |
| 071 | 22 | | PA | | 66-1 | SPARE | D04918P | | | 30 | D04620J | | | 5 | 050-099 |
| 071 | 22 | | PA | | 76-4 | SPARE | D04918P | | | 30 | D04620J | | | 5 | 150-199, 275-299 |
| 072 | 18 | | PA | | 74-3 | SPARE | D04920P | | | 12 | D04408J | | | 4 | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0570

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | | | | | |
|--------------|-----------------|----|-------|--|--------|----------|---------|-------|------|------|--------|-------|-------------|---------|------|--------|----|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type | Splice | | | |
| W0578 | 286T0578 | | | AIR COND,RECIRC FANS,CARGO HT & EQUIP COOLING (continued) | | | | | | | | | | | | | | | |
| 072 | 18 | | PA | | 84-6 | SPARE | D04920P | | 12 | | | | | D04408J | | 4 | | | 150-199, 275-299 |
| 078 | 14 | | PA | | 74-5 | 28-22-11 | D04918P | | 1 | | | | | D04408J | | 1 | FO | | 050-099 |
| 078 | 14 | | PA | | 84-6 | 28-22-11 | D04918P | | 1 | | | | | D04408J | | 1 | FO | | 150-199, 275-299 |
| 079 | 14 | | PA | | 74-5 | 28-22-11 | D04918P | | 2 | | | | | D04408J | | 2 | FO | | 050-099 |
| 079 | 14 | | PA | | 84-6 | 28-22-11 | D04918P | | 2 | | | | | D04408J | | 2 | FO | | 150-199, 275-299 |
| 080 | 14 | | PA | | 74-5 | 28-22-11 | D04918P | | 4 | | | | | D04408J | | 3 | FO | | 050-099 |
| 080 | 14 | | PA | | 84-6 | 28-22-11 | D04918P | | 4 | | | | | D04408J | | 3 | FO | | 150-199, 275-299 |
| 081 | 10 | | PA | | 73-3 | 28-22-12 | D04920P | | 5 | EN | | | | D05558J | | 1 | EO | | 050-099 |
| 081 | 10 | | PA | | 86-3 | 28-22-12 | D04920P | | 5 | EN | | | | D05558J | | 1 | EO | | 150-199, 275-299 |
| 082 | 10 | | PA | | 73-3 | 28-22-12 | D04920P | | 6 | EN | | | | D05558J | | 2 | EO | | 050-099 |
| 082 | 10 | | PA | | 86-3 | 28-22-12 | D04920P | | 6 | EN | | | | D05558J | | 2 | EO | | 150-199, 275-299 |
| 083 | 10 | | PA | | 73-3 | 28-22-12 | D04920P | | 7 | EN | | | | D05558J | | 3 | EO | | 050-099 |
| 083 | 10 | | PA | | 86-3 | 28-22-12 | D04920P | | 7 | EN | | | | D05558J | | 3 | EO | | 150-199, 275-299 |
| 085 | 24 | | PK | | 4-7 | 21-44-11 | SP02744 | | | | S | | | D00646 | | 7 | | | ALL |
| 086 | 20 | | PA | | 5-2 | 21-44-11 | D00646 | | 6 | | | | | GD00406 | | D.. | 2 | | ALL |
| 087 | 22 | | PA | | 110-5 | 21-44-21 | D05952P | | 5 | | | | | D00576 | | 7 | | | 050-099 |
| 087 | 22 | | PA | | 131-7 | 21-44-21 | D05952P | | 5 | | | | | D00576 | | 7 | | | 150-199, 275-299 |
| 088 | 20 | | PA | | 7-0 | 21-44-21 | D00576 | | 6 | | | | | GD00406 | | D.. | 2 | | ALL |
| 089 | 24 | | PK | | 2-10 | 21-44-21 | D10888 | | 3 | | | | | S00674 | | 2 | C | | 275-276 |
| 090 | 20 | | PA | | 4-1 | 21-44-21 | D10888 | | 2 | | | | | GD04750 | | D.. | E | | 275-276 |
| 091 | 20 | | PA | | 3-3 | 21-44-21 | D10888 | | 1 | | | | | GD03852 | | S.. | E | | 275-276 |
| 092 | 24 | | PK | | 124-0 | SPARE | D05952P | | | CAP | Y | | | S00674 | | CAP | Y | | 051-099 |
| 092 | 24 | | PK | | 148-0 | SPARE | D05952P | | | CAP | Y | | | S00674 | | CAP | Y | | 150-154 |
| 092 | 24 | | PK | | 148-0 | 21-44-21 | D05952P | | 7 | | | | | S00674 | | CAP | Y | | 275-276 |
| 093 | 24 | | PK | | 124-0 | SPARE | D05952P | | | CAP | Y | | | S00674 | | CAP | Y | | 051-099 |
| 093 | 24 | | PK | | 148-0 | SPARE | D05952P | | | CAP | Y | | | S00674 | | CAP | Y | | 150-154 |
| 093 | 24 | | PK | | 148-0 | 21-44-21 | D05952P | | 8 | | | | | S00674 | | CAP | Y | | 275-276 |
| 102 | 10 | | PA | | 73-5 | 28-31-21 | D04918P | | 8 | EO | | | | D05558J | | 5 | EO | | 050-099 |
| 102 | 10 | | PA | | 86-3 | 28-31-21 | D04918P | | 8 | EO | | | | D05558J | | 5 | EO | | 155-199, 276-299 |
| 107 | 10 | | PA | | 73-5 | 28-31-21 | D04918P | | 10 | EO | | | | D05558J | | 6 | EO | | 050-099 |
| 107 | 10 | | PA | | 86-3 | 28-31-21 | D04918P | | 10 | EO | | | | D05558J | | 6 | EO | | 155-199, 276-299 |
| 134 | 12 | | PA | | 6-0 | 21-73-11 | D05952P | | 14 | | | | | SP07128 | | 9 | | | 275-299 |
| 135 | 12 | | PA | | 6-0 | 21-73-11 | D05952P | | 16 | | | | | SP07130 | | 9 | | | 275-299 |
| 136 | 12 | | PA | | 6-0 | 21-73-11 | D05952P | | 18 | | | | | SP07132 | | 9 | | | 275-299 |
| 201B | 24 | | PW | C | 124-5 | 21-31-11 | D06314P | | 2 | | | | | D04918P | | 13 | | | 050-099 |
| 201B | 24 | | PW | C | 145-10 | 21-31-11 | D06314P | | 2 | | | | | D04918P | | 13 | | | 150-199, 275-299 |
| 201R | 24 | | PW | C | 0-0 | 21-31-11 | D06314P | | 3 | | | | | D04918P | | 12 | | | ALL |
| 201Z | | | | C | 0-0 | 21-31-11 | D06314P | | 4 | | | | | D04918P | | 11 | | | ALL |
| 202B | 20 | | PB | E | 124-5 | 21-31-11 | D06314P | | 6 | | | | | D04918P | | 20 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0570

Page 14

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|--------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0578 | 286T0578 | | | AIR COND,RECIRC FANS,CARGO HT & EQUIP COOLING (continued) | | | | | | | | | | | |
| 202B | 20 | PB | E | | 145-10 | 21-31-11 | D06314P | | 6 | | D04918P | | 20 | | 150-199, 275-299 |
| 202R | 20 | PB | E | | 0-0 | 21-31-11 | D06314P | | 7 | | D04918P | | 21 | | ALL |
| 801 | 22 | PA | | | 47-2 | SPARE | D04918P | | 31 | | D08044J | | 11 | | 050-099 |
| 801 | 22 | PA | | | 58-1 | SPARE | D04918P | | 31 | | D08044J | | 11 | | 150-199, 275-299 |
| 802 | 18 | PA | | | 23-2 | SPARE | D04620J | | 7 | | D08044J | | 7 | | 050-099 |
| 802 | 18 | PA | | | 24-0 | SPARE | D04620J | | 7 | | D08044J | | 7 | | 150-199, 275-299 |
| W0579 | 286T0579 | | | RUDDER RATIO AND YAW DAMPER CONT-L | | | | | | | | | | | |
| 001 | 18 | UA | | | 0-6 | 27-21-12 | D00803 | | 1 | | GD00693 | S.. | N | | ALL |
| 002 | 20 | UA | | | 27-5 | 27-21-12 | D00231 | | 2 | | D04559J | | 1 | | ALL |
| 003 | 18 | UA | | | 2-2 | 27-21-12 | D00231 | | 3 | | GD00293 | D.. | N | | ALL |
| 004 | 18 | UA | | | 3-5 | 22-21-11 | GD00279 | | | D.. | N | | 1 | | ALL |
| 005 | 18 | UA | | | 29-5 | 22-21-11 | D04559J | | 24 | DL | | | 2 | | ALL |
| 006 | 18 | UA | | | 3-8 | 22-21-11 | GD00281 | | | S.. | N | | 10 | | ALL |
| 007 | 18 | UA | | | 2-3 | 27-21-12 | D00231 | | 7 | | GD00291 | S.. | N | | ALL |
| 201B | 20 | UB | IA | | 28-2 | 27-21-12 | D00803 | | 7 | | D04559J | | 7 | | ALL |
| 201R | 20 | UB | IA | | 0-0 | 27-21-12 | D00803 | | 6 | | D04559J | | 6 | | ALL |
| 202B | 20 | UB | IB | | 27-5 | 27-21-12 | D00231 | | 6 | | D04559J | | 10 | | ALL |
| 202R | 20 | UB | IB | | 0-0 | 27-21-12 | D00231 | | 5 | | D04559J | | 9 | | ALL |
| 203B | 20 | UB | IC | | 29-5 | 22-21-11 | D04559J | | 20 | | D00245 | | 3 | | ALL |
| 203R | 20 | UB | IC | | 0-0 | 22-21-11 | D04559J | | 19 | | D00245 | | 4 | | ALL |
| 204B | 20 | UB | ID | | 29-5 | 22-21-11 | D04559J | | 22 | | D00245 | | 6 | | ALL |
| 204R | 20 | UB | ID | | 0-0 | 22-21-11 | D04559J | | 21 | | D00245 | | 5 | | ALL |
| 301B | 20 | UC | MA | | 28-2 | 27-21-12 | D00803 | | 3 | | D04559J | | 3 | | ALL |
| 301R | 20 | UC | MA | | 0-0 | 27-21-12 | D00803 | | 2 | | D04559J | | 2 | | ALL |
| 301Y | 20 | UC | MA | | 0-0 | 27-21-12 | D00803 | | 4 | | D04559J | | 4 | | ALL |
| 302B | 20 | UC | MB | | 29-5 | 22-21-11 | D04559J | | 17 | | D00245 | | 9 | | ALL |
| 302R | 20 | UC | MB | | 0-0 | 22-21-11 | D04559J | | 16 | | D00245 | | 8 | | ALL |
| 302Y | 20 | UC | MB | | 0-0 | 22-21-11 | D04559J | | 18 | | D00245 | | 7 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0570
Page 15 End
Aug 05/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0580 | 286T0580 | | | AIR COND RIGHT PACK & EQUIP COOLING | | | | | | | | | | | | | |
| 002 | 12 | | PA | 57-0 | 21-25-21 | D04922P | | 16 | | | | | D00454 | 2 | | | 050-099 |
| 002 | 12 | | PA | 67-0 | 21-25-21 | D04922P | | 16 | | | | | D00454 | 2 | | | 150-199, 275-299 |
| 003 | 12 | | PA | 57-0 | 21-25-21 | D04922P | | 18 | | | | | D00454 | 3 | | | 050-099 |
| 003 | 12 | | PA | 67-0 | 21-25-21 | D04922P | | 18 | | | | | D00454 | 3 | | | 150-199, 275-299 |
| 004 | 12 | | PA | 57-0 | 21-25-21 | D04922P | | 14 | | | | | D00454 | 4 | | | 050-099 |
| 004 | 12 | | PA | 67-0 | 21-25-21 | D04922P | | 14 | | | | | D00454 | 4 | | | 150-199, 275-299 |
| 005 | 18 | | PA | 57-0 | 21-25-21 | D04922P | | 5 | | DL | | | D00454 | 5 | | | 050-099 |
| 005 | 18 | | PA | 67-0 | 21-25-21 | D04922P | | 5 | | DL | | | D00454 | 5 | | | 150-199, 275-299 |
| 006 | 18 | | PA | 7-0 | 21-25-21 | GD00716 | | D.. | | E | | | D00454 | 6 | | | ALL |
| 007 | 12 | | PA | 7-0 | 21-25-21 | GD00718 | | S.. | | E | | | D00454 | 7 | | | ALL |
| 008 | 24 | | PK | 49-0 | 21-53-21 | D04924P | | 1 | | | | | D08048J | 1 | | | 050-099 |
| 008 | 24 | | PK | 58-0 | 21-53-21 | D04924P | | 1 | | | | | D08048J | 1 | | | 150-199, 275-299 |
| 009 | 24 | | PK | 49-0 | 21-53-21 | D04924P | | 2 | | | | | D08048J | 2 | | | 050-099 |
| 009 | 24 | | PK | 58-0 | 21-53-21 | D04924P | | 2 | | | | | D08048J | 2 | | | 150-199, 275-299 |
| 010 | 24 | | PK | 49-0 | 21-53-21 | D04924P | | 3 | | | | | D08048J | 3 | | | 050-099 |
| 010 | 24 | | PK | 58-0 | 21-53-21 | D04924P | | 3 | | | | | D08048J | 3 | | | 150-199, 275-299 |
| 011 | 24 | | PK | 49-0 | 21-53-21 | D04924P | | 4 | | | | | D08048J | 4 | | | 050-099 |
| 011 | 24 | | PK | 58-0 | 21-53-21 | D04924P | | 4 | | | | | D08048J | 4 | | | 150-199, 275-299 |
| 012 | 24 | | PK | 49-0 | 21-53-21 | D04924P | | 5 | | | | | D08048J | 5 | | | 050-099 |
| 012 | 24 | | PK | 58-0 | 21-53-21 | D04924P | | 5 | | | | | D08048J | 5 | | | 150-199, 275-299 |
| 013 | 24 | | PK | 49-0 | 21-53-21 | D04924P | | 6 | | | | | D08048J | 6 | | | 050-099 |
| 013 | 24 | | PK | 58-0 | 21-53-21 | D04924P | | 6 | | | | | D08048J | 6 | | | 150-199, 275-299 |
| 014 | 18 | | PA | 4-0 | 38-15-11 | D05824J | | 1 | | | | | D06306P | 8 | DK | | ALL |
| 015 | 18 | | PA | 4-0 | 38-15-11 | D05824J | | 2 | | | | | D06306P | 7 | DK | | ALL |
| 016 | 18 | | PA | 4-0 | 38-15-11 | D05824J | | 3 | | | | | D06306P | 6 | DK | | ALL |
| 019 | 18 | | PA | 9-0 | 38-32-11 | D05672J | | 9 | | DK | | | SP00780 | 9 | | | 050-099 |
| 019 | 18 | | PA | 10-7 | 38-32-11 | D05672J | | 9 | | DK | | | SP00780 | 9 | | | 150-155, 162-165, 275-276 |
| 019 | 18 | | PA | 10-7 | 38-32-15 | D05672J | | 9 | | DK | | | SP00780 | 9 | | | 156-157, 166-199, 277-299 |
| 020 | 24 | | PK | 48-0 | SPARE | D04636J | | 7 | | | | | D04922P | 6 | | | 050-099 |
| 020 | 24 | | PK | 59-0 | 21-51-21 | D04636J | | 7 | | | | | D04922P | 6 | | | 150-199, 275-299 |
| 022 | 18 | | PA | 4-0 | 38-32-14 | D05706J | | 8 | | | | | D06306P | 11 | DK | | ALL |
| 023 | 24 | | PV | AW | 58-0 | 21-43-11 | D02762 | | 1 | | | | D04922P | 7 | | | 050-099 |
| 023 | 24 | | PK | | 68-0 | 21-43-11 | D04922P | | 7 | | | | D02762 | 1 | | | 150-199, 275-299 |
| 023Z | | | | AW | 0-0 | 21-43-11 | D02762 | | DED | | | | D04922P | DED | | | 050-099 |
| 024 | 24 | | PV | AX | 58-0 | 21-43-11 | D02762 | | 2 | | | | D04922P | 8 | | | 050-099 |
| 024 | 24 | | PK | | 68-0 | 21-43-11 | D04922P | | 8 | | | | D02762 | 2 | | | 150-199, 275-299 |
| 024Z | | | | AX | 0-0 | 21-43-11 | D02762 | | DED | | | | D04922P | DED | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0580

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|---------|-------|------|------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0580 | 286T0580 | | | AIR COND RIGHT PACK & EQUIP COOLING (continued) | | | | | | | | | | | |
| 025 | 24 | | PK | | 51-0 | 21-43-11 | D04922P | | 9 | | SM00005 | | S | | 050-099 |
| 025 | 24 | | PK | | 61-0 | 21-43-11 | D04922P | | 9 | | SM00005 | | S | | 150-199, 275-299 |
| 026 | 24 | | PK | | 58-0 | 21-43-11 | D02762 | | 5 | | D04922P | 10 | | | 050-099 |
| 026 | 24 | | PK | | 68-0 | 21-43-11 | D04922P | | 10 | | D02762 | 5 | | | 150-199, 275-299 |
| 027 | 24 | | PK | | 7-0 | 21-43-11 | D04636J | | 8 | | SM00005 | | S | | ALL |
| 028 | 24 | | PK | | 9-0 | 21-43-11 | D02762 | | 4 | | SM00005 | | S | | ALL |
| 029 | 24 | | PK | | 48-0 | 21-43-11 | D04636J | | 11 | | D04924P | 21 | | | 050-099 |
| 029 | 24 | | PK | | 58-0 | 21-43-11 | D04636J | | 11 | | D04924P | 21 | | | 150-199, 275-299 |
| 030 | 20 | | PQ | BE | 8-0 | 21-43-11 | D02762 | | 3 | | GD05720 | A.. | E | | 050-099 |
| 030 | 20 | | PA | | 8-0 | 21-43-11 | D02762 | | 3 | | GD05720 | A.. | E | | 150-199, 275-299 |
| 030Z | | | | BE | 0-0 | 21-43-11 | D02762 | | DED | | GD05720 | DED | | | 050-099 |
| 031 | 20 | | PA | | 109-0 | 38-32-11 | D05760P | | 6 | | SP03686 | | 9 | | 050-099 |
| 031 | 20 | | PA | | 132-8 | 38-32-11 | D05760P | | 6 | | SP03686 | | 9 | | 155-199, 277-299 |
| 031 | 20 | | PA | | 132-8 | SPARE | D05760P | | 6 | | SP03686 | | 9 | | 276 |
| 032 | 20 | | PA | | 8-0 | 21-43-11 | D02762 | | 7 | | GD00716 | D.. | E | | ALL |
| 033 | 24 | | PK | | 49-0 | 21-43-11 | D04924P | | 7 | | D04636J | 2 | | | 050-099 |
| 033 | 24 | | PK | | 58-0 | 21-43-11 | D04924P | | 7 | | D04636J | 2 | | | 150-199, 275-299 |
| 034 | 24 | | PK | | 49-0 | 21-43-11 | D04924P | | 8 | | D04636J | 1 | | | 050-099 |
| 034 | 24 | | PK | | 58-0 | 21-43-11 | D04924P | | 8 | | D04636J | 1 | | | 150-199, 275-299 |
| 035 | 20 | | PA | | 58-0 | 21-43-11 | D04924P | | 9 | | D02766 | 1 | | | 050-099 |
| 035 | 20 | | PA | | 53-0 | 21-43-11 | D04924P | | 9 | | D02766 | 1 | | | 150-199, 275-299 |
| 036 | 20 | | PA | | 13-0 | 21-43-11 | D02766 | | 2 | | GD00268 | D.. | 2 | | 050-099 |
| 036 | 20 | | PA | | 10-0 | 21-43-11 | D02766 | | 2 | | GD04780 | D.. | 2 | | 150-199, 275-299 |
| 038 | 24 | | PK | | 58-0 | 21-43-11 | D02762 | | 6 | | D04924P | 23 | | | 050-099 |
| 038 | 24 | | PK | | 68-0 | 21-43-11 | D02762 | | 6 | | D04924P | 23 | | | 150-199, 275-299 |
| 039 | 10 | | PA | | 66-0 | 28-31-21 | D05760P | | 5 | EN | D05508J | 4 | EO | | 050-099 |
| 039 | 10 | | PA | | 76-0 | 28-31-21 | D05760P | | 5 | EN | D05508J | 4 | EO | | 155-199, 276-299 |
| 041 | 12 | | PA | | 4-0 | 38-32-11 | D06306P | | 20 | | D05706J | 1 | | | ALL |
| 042 | 12 | | PA | | 4-0 | 38-32-11 | D06306P | | 22 | | D05706J | 2 | | | ALL |
| 043 | 12 | | PA | | 4-0 | 38-32-11 | D06306P | | 24 | | D05706J | 3 | | | ALL |
| 044 | 22 | | PA | | 4-0 | 38-32-11 | D06306P | | 9 | | D05672J | 8 | | | ALL |
| 045 | 18 | | PA | | 4-0 | 38-32-14 | D05706J | | 7 | | D06306P | 10 | DK | | 050-099, 150-154, 275-276 |
| 051 | 10 | | PA | | 66-0 | 28-31-21 | D05760P | | 7 | EN | D05508J | 5 | EO | | 050-099 |
| 051 | 10 | | PA | | 76-0 | 28-31-21 | D05760P | | 7 | EN | D05508J | 5 | EO | | 155-199, 276-299 |
| 052 | 10 | | PA | | 66-0 | 28-31-21 | D05760P | | 8 | EN | D05508J | 6 | EO | | 050-099 |
| 052 | 10 | | PA | | 76-0 | 28-31-21 | D05760P | | 8 | EN | D05508J | 6 | EO | | 155-199, 276-299 |
| 053 | 22 | | PQ | CC | 25-0 | 38-32-15 | D05672J | | 16 | | SP00550 | | 9 | | 156, 166 |
| 053 | 22 | | PQ | CC | 24-0 | 38-32-15 | D05672J | | 16 | | SP00550 | | 9 | | 157, 167-199, 277-299 |

WIRE LIST

D280T132

91-21-11
 Section W0580
 Page 2
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0580 | 286T0580 | | | AIR COND RIGHT PACK & EQUIP COOLING (continued) | | | | | | | | | | | |
| 053 | 22 | | PA | 10-0 | 38-32-14 | D05672J | | 13 | | | SP05398 | | 9 | | 275-276 |
| 053Z | | | | 0-0 | 38-32-15 | D05672J | | DED | | | SP00550 | DED | | | 156-157, 166-199, 277-299 |
| 054 | 22 | | PA | 10-0 | 38-32-14 | D05672J | | 14 | | | SP05400 | | 9 | | 275-276 |
| 055 | 22 | | PA | 10-7 | 38-32-14 | D05672J | | 15 | | | SP03686 | | 9 | | 275-276 |
| 057 | 20 | | PA | 10-0 | 38-32-15 | D05672J | | 20 | | | SP05430 | | 9 | | 156, 166 |
| 057 | 20 | | PA | 10-7 | 38-32-15 | D05672J | | 20 | | | SP05430 | | 9 | | 157, 167-199, 277-299 |
| 058 | 20 | | PA | 10-0 | 38-32-15 | D05672J | | 21 | | | SP05428 | | 9 | | 156, 166 |
| 058 | 20 | | PA | 10-7 | 38-32-15 | D05672J | | 21 | | | SP05428 | | 9 | | 157, 167-199, 277-299 |
| 059 | 20 | | PQ | 25-0 | 38-32-15 | D05672J | CI | 18 | | | SP00268 | | 9 | | 156, 166 |
| 059 | 20 | | PQ | 24-0 | 38-32-15 | D05672J | CI | 18 | | | SP00268 | | 9 | | 157, 167-199, 277-299 |
| 059Z | | | | 0-0 | 38-32-15 | D05672J | CI | DED | | | SP00268 | DED | | | 156-157, 166-199, 277-299 |
| 060 | 20 | | PQ | 25-0 | 38-32-15 | D05672J | CJ | 19 | | | SP05436 | | 9 | | 156, 166 |
| 060 | 20 | | PQ | 24-0 | 38-32-15 | D05672J | CJ | 19 | | | SP05436 | | 9 | | 157, 167-199, 277-299 |
| 060Z | | | | 0-0 | 38-32-15 | D05672J | CJ | DED | | | SP05436 | DED | | | 156-157, 166-199, 277-299 |
| 086 | 24 | | PK | 105-0 | 21-44-11 | D04924P | | 10 | | | D05672J | | 1 | | 050-099 |
| 086 | 24 | | PK | 125-0 | 21-44-11 | D04924P | | 10 | | | D05672J | | 1 | | 150-199, 275-299 |
| 087 | 22 | | PA | 105-0 | 21-44-11 | D04924P | | 11 | | | D05672J | | 2 | | 050-099 |
| 087 | 22 | | PA | 125-0 | 21-44-11 | D04924P | | 11 | | | D05672J | | 2 | | 150-199, 275-299 |
| 088 | 24 | | PK | 105-0 | 21-44-11 | D04924P | | 12 | | | D05672J | | 3 | | 050-099 |
| 088 | 24 | | PK | 125-0 | 21-44-11 | D04924P | | 12 | | | D05672J | | 3 | | 150-199, 275-299 |
| 090 | 20 | | PA | 5-0 | 21-44-11 | D00706 | | 4 | | | GD04212 | D.. | E | | 050-099 |
| 090 | 20 | | PA | 4-0 | 21-44-11 | D00706 | | 4 | | | GD04212 | D.. | E | | 150-199, 275-299 |
| 091 | 20 | | PA | 5-0 | 21-44-11 | D00706 | | 3 | | | GD01146 | A.. | E | | 050-099 |
| 091 | 20 | | PA | 4-0 | 21-44-11 | D00706 | | 3 | | | GD01146 | A.. | E | | 150-199, 275-299 |
| 092 | 22 | | PA | 5-0 | 21-44-11 | D00706 | | 5 | | | SP00460 | | S | | 050-099, 280-299 |
| 092 | 22 | | PA | 6-0 | 21-44-11 | D00706 | | 5 | | | SP00460 | | S | | 150-199, 275-278 |
| 093 | 12 | | PA | 105-0 | 38-32-11 | D05760P | | 1 | | | D05706J | | 4 | | 050-099 |
| 093 | 12 | | PA | 125-0 | 38-32-11 | D05760P | | 1 | | | D05706J | | 4 | | 150-199, 275-299 |
| 094 | 12 | | PA | 105-0 | 38-32-11 | D05760P | | 2 | | | D05706J | | 5 | | 050-099 |
| 094 | 12 | | PA | 125-0 | 38-32-11 | D05760P | | 2 | | | D05706J | | 5 | | 150-199, 275-299 |
| 095 | 12 | | PA | 105-0 | 38-32-11 | D05760P | | 3 | | | D05706J | | 6 | | 050-099 |
| 095 | 12 | | PA | 125-0 | 38-32-11 | D05760P | | 3 | | | D05706J | | 6 | | 150-199, 275-299 |
| 097 | 14 | | PA | 104-2 | 21-26-11 | D04924P | | 20 | | | D06306P | | 14 | | 050-099 |
| 097 | 14 | | PA | 125-0 | 21-26-11 | D04924P | | 20 | | | D06306P | | 14 | | 150-199, 275-299 |
| 098 | 14 | | PA | 104-2 | 21-26-11 | D04924P | | 22 | | | D06306P | | 16 | | 050-099 |
| 098 | 14 | | PA | 125-0 | 21-26-11 | D04924P | | 22 | | | D06306P | | 16 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0580

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0580 | 286T0580 | | | AIR COND RIGHT PACK & EQUIP COOLING (continued) | | | | | | | | | | | | | | |
| 099 | 14 | | PA | | 104-2 | 21-26-11 | D04924P | | 24 | | | | D06306P | | 18 | | | 050-099 |
| 099 | 14 | | PA | | 125-0 | 21-26-11 | D04924P | | 24 | | | | D06306P | | 18 | | | 150-199, 275-299 |
| 103 | 24 | | PK | | 104-2 | 21-26-11 | D06306P | | 1 | | | | D04924P | | 19 | | | 050-099 |
| 103 | 24 | | PK | | 125-0 | 21-26-11 | D06306P | | 1 | | | | D04924P | | 19 | | | 150-199, 275-299 |
| 107 | 24 | | PK | | 105-0 | 21-44-11 | D04924P | | 13 | | | | D05672J | | 4 | | | 050-099 |
| 107 | 24 | | PK | | 125-0 | 21-44-11 | D04924P | | 13 | | | | D05672J | | 4 | | | 150-199, 275-299 |
| 108 | 24 | | PK | | 61-0 | 21-44-11 | D05672J | | 7 | | | | D00706 | | 1 | | | 050-099 |
| 108 | 24 | | PK | | 83-0 | 21-44-11 | D05672J | | 7 | | | | D00706 | | 1 | | | 150-199, 275-299 |
| 109 | 24 | | PK | | 61-0 | 21-44-11 | D05672J | | 6 | | | | D00706 | | 2 | | | 050-099 |
| 109 | 24 | | PK | | 83-0 | 21-44-11 | D05672J | | 6 | | | | D00706 | | 2 | | | 150-199, 275-299 |
| 110 | 24 | | PK | | 58-0 | 21-44-11 | D05672J | | 5 | | | | D05948J | | 1 | | | 050-099 |
| 110 | 24 | | PK | | 72-0 | 21-44-11 | D05672J | | 5 | | | | D05948J | | 1 | | | 150-199, 275-299 |
| 111 | 20 | | PA | | 105-0 | 36-11-41 | D04922P | | 4 | | | | D05824J | | 8 | | | 050-099 |
| 111 | 20 | | PA | | 126-0 | 36-11-41 | D04922P | | 4 | | | | D05824J | | 8 | | | 150-199, 275-299 |
| 112 | 22 | | PA | | 103-0 | 21-26-21 | D04922P | | 19 | | | | D06306P | | 3 | | | 050-099 |
| 112 | 22 | | PA | | 125-0 | 21-26-21 | D04922P | | 19 | | | | D06306P | | 3 | | | 150-199, 275-299 |
| 113 | 22 | | PA | | 103-0 | 21-26-21 | D04922P | | 21 | | | | D06306P | | 4 | | | 050-099 |
| 113 | 22 | | PA | | 125-0 | 21-26-21 | D04922P | | 21 | | | | D06306P | | 4 | | | 150-199, 275-299 |
| 114 | 22 | | PA | | 103-0 | 21-26-21 | D04922P | | 23 | | | | D06306P | | 5 | | | 050-099 |
| 114 | 22 | | PA | | 125-0 | 21-26-21 | D04922P | | 23 | | | | D06306P | | 5 | | | 150-199, 275-299 |
| 115 | 22 | | PA | | 117-0 | 21-44-21 | D04922P | | 25 | | | | D00606 | | 1 | | | 050-099 |
| 115 | 22 | | PA | | 139-0 | 21-44-21 | D04922P | | 25 | | | | D00606 | | 1 | | | 150-199, 275-299 |
| 116 | 22 | | PA | | 117-0 | 21-44-21 | D04922P | | 15 | | | | D00606 | | 2 | | | 050-099 |
| 116 | 22 | | PA | | 139-0 | 21-44-21 | D04922P | | 15 | | | | D00606 | | 2 | | | 150-199, 275-299 |
| 118 | 20 | | PA | | 5-0 | 21-44-21 | D00606 | | 3 | | | | GD01140 | | A.. | E | | 050-099 |
| 118 | 20 | | PA | | 4-0 | 21-44-21 | D00606 | | 3 | | | | GD01140 | | A.. | E | | 150-199, 275-299 |
| 119 | 20 | | PA | | 5-0 | 21-44-21 | D00606 | | 4 | | | | GD04212 | | D.. | E | | 050-099 |
| 119 | 20 | | PA | | 4-0 | 21-44-21 | D00606 | | 4 | | | | GD04212 | | D.. | E | | 150-199, 275-299 |
| 120 | 22 | | PA | | 5-0 | 21-44-21 | D00606 | | 5 | | | | SP01464 | | | S | | ALL |
| 121 | 24 | | PV | N | 48-0 | 21-51-21 | D04922P | | 1 | | | | D04636J | | 3 | | | 050-099 |
| 121 | 24 | | PV | N | 58-0 | 21-51-21 | D04922P | | 1 | | | | D04636J | | 3 | | | 150-199, 275-299 |
| 121Z | | | | N | 0-0 | 21-51-21 | D04922P | | DED | | | | D04636J | | DED | | | ALL |
| 122 | 24 | | PV | O | 48-0 | 21-51-21 | D04922P | | 2 | | | | D04636J | | 4 | | | 050-099 |
| 122 | 24 | | PV | O | 58-0 | 21-51-21 | D04922P | | 2 | | | | D04636J | | 4 | | | 150-199, 275-299 |
| 122Z | | | | O | 0-0 | 21-51-21 | D04922P | | DED | | | | D04636J | | DED | | | ALL |
| 123 | 24 | | PV | P | 48-0 | 21-51-21 | D04922P | | 3 | | | | D04636J | | 5 | | | 050-099 |
| 123 | 24 | | PV | P | 58-0 | 21-51-21 | D04922P | | 3 | | | | D04636J | | 5 | | | 150-199, 275-299 |
| 123Z | | | | P | 0-0 | 21-51-21 | D04922P | | DED | | | | D04636J | | DED | | | ALL |
| 124 | 24 | | PV | Q | 48-0 | 21-51-21 | D04922P | | 17 | | | | D04636J | | 6 | | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0580
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0580 | 286T0580 | AIR COND RIGHT PACK & EQUIP COOLING (continued) | | | | | | | | | | | | | | |
| 124 | 24 | PV | Q | 58-0 | 21-51-21 | D04922P | | 17 | | D04636J | | 6 | | 150-199, 275-299 | | |
| 124Z | | | Q | 0-0 | 21-51-21 | D04922P | | DED | | D04636J | | DED | | ALL | | |
| 131 | 18 | PA | | 76-0 | SPARE | D05760P | | 6 | | D04410J | | 4 | | 150-154, 275 | | |
| 132 | 24 | PK | | 103-0 | 21-26-21 | D04922P | | 11 | | D06306P | | 2 | | 050-099 | | |
| 132 | 24 | PK | | 125-0 | 21-26-21 | D04922P | | 11 | | D06306P | | 2 | | 150-199, 275-299 | | |
| 138 | 14 | PA | | 68-0 | 28-22-11 | D04922P | | 20 | | D04410J | | 1 | FO | 050-099 | | |
| 138 | 14 | PA | | 76-0 | 28-22-11 | D04922P | | 20 | | D04410J | | 1 | FO | 150-199, 275-299 | | |
| 139 | 14 | PA | | 68-0 | 28-22-11 | D04922P | | 22 | | D04410J | | 2 | FO | 050-099 | | |
| 139 | 14 | PA | | 76-0 | 28-22-11 | D04922P | | 22 | | D04410J | | 2 | FO | 150-199, 275-299 | | |
| 140 | 14 | PA | | 68-0 | 28-22-11 | D04922P | | 24 | | D04410J | | 3 | FO | 050-099 | | |
| 140 | 14 | PA | | 76-0 | 28-22-11 | D04922P | | 24 | | D04410J | | 3 | FO | 150-199, 275-299 | | |
| 141 | 10 | PA | | 67-0 | 28-22-12 | D04924P | | 14 | EN | D05508J | | 1 | EO | 050-099 | | |
| 141 | 10 | PA | | 76-0 | 28-22-12 | D04924P | | 14 | EN | D05508J | | 1 | EO | 150-199, 275-299 | | |
| 142 | 10 | PA | | 67-0 | 28-22-12 | D04924P | | 16 | EN | D05508J | | 2 | EO | 050-099 | | |
| 142 | 10 | PA | | 76-0 | 28-22-12 | D04924P | | 16 | EN | D05508J | | 2 | EO | 150-199, 275-299 | | |
| 143 | 10 | PA | | 67-0 | 28-22-12 | D04924P | | 18 | EN | D05508J | | 3 | EO | 050-099 | | |
| 143 | 10 | PA | | 76-0 | 28-22-12 | D04924P | | 18 | EN | D05508J | | 3 | EO | 150-199, 275-299 | | |
| 144 | 20 | PA | | 10-0 | 25-33-11 | SP02594 | | | 9 | D04924P | | 15 | | 150-154, 275-276 | | |
| 145 | 20 | PA | | 10-0 | 25-33-11 | SP02596 | | | 9 | D04924P | | 17 | | 150-154, 275-276 | | |
| 149 | 24 | PK | | 60-0 | 21-44-11 | SP02744 | | | S | D05672J | | 12 | | 050-099 | | |
| 149 | 24 | PK | | 83-0 | 21-44-11 | SP02744 | | | S | D05672J | | 12 | | 150-199, 275-299 | | |
| 201B | 24 | PW | U | 49-0 | 21-51-21 | D04922P | | 12 | | D04636J | | 9 | | 050-099 | | |
| 201B | 24 | PW | U | 58-0 | 21-51-21 | D04922P | | 12 | | D04636J | | 9 | | 150-199, 275-299 | | |
| 201R | 24 | PW | U | 0-0 | 21-51-21 | D04922P | | 13 | | D04636J | | 10 | | ALL | | |
| 201Z | | | U | 0-0 | 21-51-21 | D04922P | | DED | | D04636J | | DED | | ALL | | |
| W0581 | 286T0581 | STAB.POS XMTR & STAB.TRIM CONT R | | | | | | | | | | | | | | |
| 001 | 20 | UA | | 27-0 | 27-41-21 | D04533J | | 6 | | D02219 | | 3 | | 050-099, 155-199, 275-299 | | |
| 001 | 20 | UA | | 27-0 | 27-41-21 | D04533J | | 6 | | D00247 | | 3 | | 150-154 | | |
| 002 | 20 | UA | | 27-0 | 27-41-21 | D04533J | | 7 | | D02219 | | 2 | | 050-099, 155-199, 275-299 | | |
| 002 | 20 | UA | | 27-0 | 27-41-21 | D04533J | | 7 | | D00247 | | 2 | | 150-154 | | |
| 003 | 18 | UA | | 2-11 | 27-41-21 | GD00259 | | D.. | N | D02219 | | 1 | DK | 050-099, 155-199, 275-299 | | |
| 003 | 18 | UA | | 4-0 | 27-41-21 | GD00259 | | D.. | N | D00247 | | 1 | DK | 150-154 | | |
| 004Y | 20 | XP | | 19-8 | 27-41-21 | D02217 | | 2 | | D00239 | | 17 | | 050-099, 155-199, 275-299 | | |
| 004Y | 20 | XP | | 20-0 | 27-41-21 | D00237 | | 13 | | D00239 | | 17 | | 150-154 | | |

WIRE LIST

D280T132

91-21-11

Section W0580

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0581 | 286T0581 | | | STAB.POS XMTR & STAB.TRIM CONT R (continued) | | | | | | | | | | | |
| 005Y | 18 | | XP | 4-3 | 27-41-21 | D02217 | | 1 | | | GD00259 | D.. | N | | 050-099, 155-199, 275-299 |
| 005Y | 18 | | XP | 5-0 | 27-41-21 | D00237 | | 12 | DK | | GD00259 | D.. | N | | 150-154 |
| 006Y | 20 | | XP | 19-8 | 27-41-21 | D02217 | | 6 | | | D00239 | 21 | | | 050-099, 155-199, 275-299 |
| 006Y | 20 | | XP | 20-0 | 27-41-21 | D00237 | | 8 | | | D00239 | 21 | | | 150-154 |
| 007Y | 18 | | XP | 4-3 | 27-41-21 | D02217 | | 5 | | | GD00259 | D.. | N | | 050-099, 155-199, 275-299 |
| 007Y | 18 | | XP | 5-0 | 27-41-21 | D00237 | | 7 | DK | | GD00259 | D.. | N | | 150-154 |
| 009 | 18 | | UA | 2-10 | 27-41-21 | D02219 | | 8 | DK | | GD00675 | S.. | N | | 050-099, 155-199, 275-299 |
| 009 | 18 | | UA | 4-0 | 27-41-21 | D00247 | | 8 | DK | | GD00675 | S.. | N | | 150-154 |
| 010Y | 20 | | XP | 34-6 | 27-41-21 | D00239 | | 20 | | | D04533J | 10 | | | 050-099, 155-199, 275-299 |
| 010Y | 20 | | XP | 35-0 | 27-41-21 | D00239 | | 20 | | | D04533J | 10 | | | 150-154 |
| 011Y | 20 | | XP | 34-6 | 27-41-21 | D00239 | | 19 | | | D04533J | 8 | | | 050-099 |
| 011Y | 20 | | XP | 35-0 | 27-41-21 | D00239 | | 16 | | | D04533J | 8 | | | 150-154 |
| 011Y | 20 | | XP | 34-6 | 27-41-21 | D00239 | | 16 | | | D04533J | 8 | | | 155-199, 275-299 |
| 012Y | 20 | | XP | 34-6 | 27-41-21 | D00239 | | 16 | | | D04533J | 9 | | | 050-099 |
| 013Y | 18 | | XP | 4-1 | 27-41-21 | D02217 | | 10 | | | GD00675 | S.. | N | | 050-099, 155-199, 275-299 |
| 013Y | 18 | | XP | 5-0 | 27-41-21 | D00237 | | 6 | DK | | GD00675 | S.. | N | | 150-154 |
| 015 | 18 | | UA | 4-9 | 27-48-11 | D00239 | | 10 | DK | | GD00539 | A.. | N | | 050-099, 155-156, 162-166, 275-276 |
| 015 | 18 | | UA | 5-0 | 27-48-11 | D00239 | | 10 | DK | | GD00539 | A.. | N | | 150-154 |
| 016 | 18 | | UA | 4-9 | 27-48-11 | D00239 | | 12 | DK | | GD00539 | A.. | N | | 050-099, 155-199, 275-299 |
| 016 | 18 | | UA | 5-0 | 27-48-11 | D00239 | | 12 | DK | | GD00539 | A.. | N | | 150-154 |
| 017 | 20 | | UA | 34-6 | 27-48-11 | D00239 | | 11 | | | D04533J | 1 | | | 050-099, 157-164, 167-199, 275-299 |
| 017 | 20 | | UA | 35-0 | 27-48-11 | D00239 | | 11 | | | D04533J | 1 | | | 150-154 |
| 018 | 20 | | UA | 34-11 | 27-48-11 | D00239 | | 9 | | | D04531J | 2 | | | 050 |
| 018 | 20 | | UA | 36-0 | 27-48-11 | D00239 | | 9 | | | D04531J | 2 | | | 051-099 |
| 018 | 20 | | UA | 35-0 | 27-48-11 | D00239 | | 9 | | | D04533J | 2 | | | 150-154 |
| 018 | 20 | | UA | 34-6 | 27-48-11 | D00239 | | 9 | | | D04533J | 2 | | | 162-164, 275-276 |
| 019 | 20 | | UA | 34-11 | 27-48-11 | D00239 | | 8 | | | D04531J | 3 | | | 050 |
| 019 | 20 | | UA | 36-0 | 27-48-11 | D00239 | | 8 | | | D04531J | 3 | | | 051-099 |
| 019 | 20 | | UA | 35-0 | 27-48-11 | D00239 | | 8 | | | D04533J | 3 | | | 150-154 |
| 019 | 20 | | UA | 34-6 | 27-48-11 | D00239 | | 8 | | | D04533J | 3 | | | 162-164, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0580

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0581 | 286T0581 | | | STAB.POS XMTR & STAB.TRIM CONT R (continued) | | | | | | | | | | | | |
| 020 | 18 | | UA | 4-9 | 27-58-21 | D00239 | 31 | DK | | GD00579 | S.. | N | | 050-099, 155-199, 275-299 | | |
| 020 | 18 | | UA | 5-0 | 27-58-21 | D00239 | 31 | DK | | GD00579 | S.. | N | | 150-154 | | |
| 021Y | 20 | | XP | 35-10 | 27-41-21 | SP00393 | | 9 | | D00239 | 18 | | | 050-099, 155-199, 275-299 | | |
| 021Y | 20 | | XP | 35-0 | 27-41-21 | D00239 | 18 | | | SP00393 | | 9 | | 150-154 | | |
| 022Y | 20 | | XP | 42-0 | 27-41-31 | D02217 | 8 | | | D06023J | 1 | | | 050-099, 155-199, 275-299 | | |
| 023Y | 20 | | XP | 42-0 | 27-41-31 | D02217 | 4 | | | D06023J | 2 | | | 050-099, 155-199, 275-299 | | |
| 024Y | 18 | | XP | 3-11 | 27-41-31 | D02217 | 3 | | | GD00759 | D.. | N | | 050-099, 155-199, 275-299 | | |
| 025Y | 18 | | XP | 3-11 | 27-41-31 | D02217 | 7 | | | GD00759 | D.. | N | | 050-099, 155-199, 275-299 | | |
| 201B | 20 | | UB IA | 34-6 | 27-58-21 | D00239 | 1 | | | D04533J | 11 | | | 050-099, 155-199, 275-299 | | |
| 201B | 20 | | UB IA | 35-0 | 27-58-21 | D00239 | 1 | | | D04533J | 11 | | | 150-154 | | |
| 201R | 20 | | UB IA | 0-0 | 27-58-21 | D00239 | 7 | | | D04533J | 12 | | | ALL | | |
| 301B | 20 | | UC MA | 34-6 | 27-58-21 | D00239 | 2 | | | D04533J | 13 | | | 050-099, 155-199, 275-299 | | |
| 301B | 20 | | UC MA | 35-0 | 27-58-21 | D00239 | 2 | | | D04533J | 13 | | | 150-154 | | |
| 301R | 20 | | UC MA | 0-0 | 27-58-21 | D00239 | 3 | | | D04533J | 14 | | | ALL | | |
| 301Y | 20 | | UC MA | 0-0 | 27-58-21 | D00239 | 4 | | | D04533J | 15 | | | ALL | | |
| 302B | 20 | | UC MB | 34-6 | 27-48-11 | D00239 | 9 | | | D04533J | 2 | | | 155-157, 165-199, 277-299 | | |
| 302R | 20 | | UC MB | 0-0 | 27-48-11 | D00239 | 8 | | | D04533J | 3 | | | 155-157, 165-199, 277-299 | | |
| 302Y | 20 | | UC MB | 0-0 | 27-48-11 | D00239 | 11 | | | D04533J | 1 | | | 155-156, 165-166 | | |
| 302Y | 20 | | UC MB | 0-0 | 27-48-11 | D00239 | 10 | | | D04533J | 4 | | | 157, 167-199, 277-299 | | |
| W0583 | 286T0583 | | | RUDDER RATIO AND YAW DAMPER CONT-R | | | | | | | | | | | | |
| 001 | 18 | | UA | 0-8 | 27-21-22 | D00805 | 1 | | | GD00695 | S.. | N | | ALL | | |
| 004 | 18 | | UA | 29-1 | 22-21-21 | D00233 | 2 | | | D04567J | 15 | DL | | ALL | | |
| 005 | 18 | | UA | 3-3 | 22-21-21 | D00233 | 1 | | | GD00283 | D.. | N | | ALL | | |
| 006 | 18 | | UA | 3-4 | 22-21-21 | D00233 | 10 | | | GD00285 | S.. | N | | ALL | | |
| 201B | 20 | | UB IA | 27-2 | 27-21-22 | D00805 | 7 | | | D04567J | 7 | | | ALL | | |
| 201R | 20 | | UB IA | 0-0 | 27-21-22 | D00805 | 6 | | | D04567J | 6 | | | ALL | | |
| 202B | 20 | | UB IB | 26-5 | 27-21-22 | D00243 | 2 | | | D04567J | 10 | | | ALL | | |
| 202R | 20 | | UB IB | 0-0 | 27-21-22 | D00243 | 1 | | | D04567J | 9 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0580

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0583 | 286T0583 | | | RUDDER RATIO AND YAW DAMPER CONT-R (continued) | | | | | | | | | | | |
| 203B | 20 | UB | IC | | 29-1 | 22-21-21 | D00233 | | 3 | | D04567J | | 19 | | ALL |
| 203R | 20 | UB | IC | | 0-0 | 22-21-21 | D00233 | | 4 | | D04567J | | 18 | | ALL |
| 204B | 20 | UB | ID | | 29-1 | 22-21-21 | D00233 | | 6 | | D04567J | | 24 | | ALL |
| 204R | 20 | UB | ID | | 0-0 | 22-21-21 | D00233 | | 5 | | D04567J | | 23 | | ALL |
| 301B | 20 | UC | MA | | 27-2 | 27-21-22 | D00805 | | 3 | | D04567J | | 3 | | ALL |
| 301R | 20 | UC | MA | | 0-0 | 27-21-22 | D00805 | | 2 | | D04567J | | 2 | | ALL |
| 301Y | 20 | UC | MA | | 0-0 | 27-21-22 | D00805 | | 4 | | D04567J | | 4 | | ALL |
| 302B | 20 | UC | MB | | 29-1 | 22-21-21 | D00233 | | 9 | | D04567J | | 21 | | ALL |
| 302R | 20 | UC | MB | | 0-0 | 22-21-21 | D00233 | | 8 | | D04567J | | 20 | | ALL |
| 302Y | 20 | UC | MB | | 0-0 | 22-21-21 | D00233 | | 7 | | D04567J | | 22 | | ALL |
| W0584 | 286T0584 | | | PLT AUX HTR,L WINDSHIELD WIPER & RAIN REPELLANT. | | | | | | | | | | | |
| 001 | 22 | PA | | | 23-0 | 30-43-11 | D04966J | | 1 | | D04704J | | 1 | | ALL |
| 005 | 18 | PA | | | 23-0 | 30-42-11 | D04966J | | 7 | | D04704J | | 7 | | ALL |
| 008 | 20 | PA | | | 2-0 | 21-45-11 | SM00002 | | | 9 | D03780 | | 7 | | ALL |
| 009 | 20 | PA | | | 15-0 | 21-45-11 | D04966J | | 3 | | SM00001 | | 9 | | ALL |
| 010 | 20 | PA | | | 11-0 | 21-45-11 | D02962 | | 1 | | D03780 | | 4 | | ALL |
| 011 | 20 | PA | | | 8-0 | 21-45-11 | D02962 | | 2 | | SM00001 | | 9 | | ALL |
| 012 | 20 | PA | | | 3-0 | 21-45-11 | D02962 | | 3 | | GD01226 | S.. | E | | ALL |
| 013 | 20 | PA | | | 23-0 | 21-45-11 | D02960 | | 1 | | D03780 | | 10 | | ALL |
| 014 | 20 | PA | | | 21-0 | 21-45-11 | D02960 | | 2 | | SM00001 | | 9 | | ALL |
| 015 | 20 | PA | | | 6-0 | 21-45-11 | D02960 | | 3 | | GD00561 | S.. | 2 | | ALL |
| 016 | 20 | PA | | | 5-0 | 21-45-11 | D03780 | | 3 | | GD00027 | A.. | 2 | | ALL |
| 017 | 20 | PA | | | 9-0 | 33-13-11 | D03780 | | 1 | | SP03774 | | W | | ALL |
| 018 | 20 | PA | | | 7-0 | 33-13-11 | D03780 | | 2 | | GD00027 | A.. | 2 | | ALL |
| 025 | 18 | PA | | | 23-0 | 30-42-11 | D04966J | | 10 | | D04704J | | 10 | | ALL |
| 027 | 16 | PA | | | 23-0 | 30-42-11 | D04966J | | 4 | | D04704J | | 4 | | ALL |
| 028 | 20 | PA | | | 22-0 | 21-45-11 | D04966J | | 2 | | SM00002 | | 9 | | ALL |
| 029 | 20 | PA | | | 2-0 | 21-45-11 | D03780 | | 8 | | SM00002 | | 9 | | ALL |
| 031 | 18 | PA | | | 9-0 | 33-13-11 | D06348J | | 1 | DL | SP03774 | | W | | ALL |
| 032 | 18 | PA | | | 8-0 | 33-13-11 | SP03776 | | | W | GD00027 | A.. | 2 | | ALL |
| 037 | 20 | PA | | | 3-0 | SPARE | D04704J | | 2 | | D06348J | | 2 | | ALL |
| W0585 | 286T0585 | | | E1-1 TO E2-1 SHELF | | | | | | | | | | | |
| 001 | 22 | PA | | | 9-0 | 22-21-21 | D05323P | | 1 | | D05293P | | 1 | | ALL |
| 002 | 22 | PA | | | 9-0 | 22-22-11 | D05323P | | 2 | | D05293P | | 2 | | ALL |
| 003 | 22 | PA | | | 9-0 | 22-22-11 | D05323P | | 3 | | D05293P | | 3 | | ALL |
| 004 | 22 | PA | | | 9-0 | 22-22-11 | D05323P | | 4 | | D05293P | | 4 | | ALL |
| 005 | 22 | PA | | | 9-0 | 22-24-11 | D05323P | | 5 | | D05293P | | 5 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0580
 Page 8
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0585 | 286T0585 | | | E1-1 TO E2-1 SHELF (continued) | | | | | | | | | | | | |
| 006 | 22 | | PA | 9-0 | 27-09-12 | D05323P | | 6 | | | | D05293P | 6 | | ALL | |
| 007 | 22 | | PA | 9-0 | 27-09-13 | D05323P | | 7 | | | | D05293P | 7 | | ALL | |
| 008 | 22 | | PA | 9-0 | 27-09-13 | D05323P | | 8 | | | | D05293P | 8 | | ALL | |
| 014 | 22 | | PA | 9-0 | SPARE | D05323P | | 14 | | | | D05293P | 14 | | ALL | |
| 015 | 22 | | PA | 9-0 | 27-61-11 | D05323P | | 15 | | | | D05293P | 15 | | ALL | |
| 016 | 22 | | PA | 9-0 | SPARE | D05323P | | 16 | | | | D05293P | 16 | | ALL | |
| 017 | 20 | | PA | 9-0 | SPARE | D05323P | | 17 | | | | D05293P | 17 | | ALL | |
| 018 | 20 | | PA | 9-0 | SPARE | D05323P | | 18 | | | | D05293P | 18 | | ALL | |
| 201B | 24 | | PW IA | 9-0 | 22-21-21 | D05323P | | 10 | | | | D05293P | 10 | | ALL | |
| 201R | 24 | | PW IA | 0-0 | 22-21-21 | D05323P | | 9 | | | | D05293P | 9 | | ALL | |
| 201Z | | | IA | 0-0 | 22-21-21 | D05323P | | 11 | | | | D05293P | 11 | | ALL | |
| 202B | 24 | | PW IB | 9-0 | 22-22-11 | D05323P | | 20 | | | | D05293P | 20 | | ALL | |
| 202R | 24 | | PW IB | 0-0 | 22-22-11 | D05323P | | 19 | | | | D05293P | 19 | | ALL | |
| 202Z | | | IB | 0-0 | 22-22-11 | D05323P | | 21 | | | | D05293P | 21 | | ALL | |
| W0586 | 286T0586 | | | CO-PLT AUX HTR,R WINDSHIELD WIPER & RAIN REPELLANT | | | | | | | | | | | | |
| 001 | 22 | | PA | 24-0 | 30-43-11 | D04970J | | 1 | | | | D04706J | 1 | | ALL | |
| 005 | 18 | | PA | 24-0 | 30-42-11 | D04970J | | 7 | | | | D04706J | 7 | | ALL | |
| 006 | 20 | | PA | 21-0 | 21-45-11 | D04970J | | 2 | | | | SM00002 | | 9 | ALL | |
| 007 | 20 | | PA | 5-0 | 21-45-11 | D03762 | | 8 | | | | SM00002 | | 9 | ALL | |
| 008 | 20 | | PA | 5-0 | 21-45-11 | SM00002 | | | 9 | | | D03762 | 7 | | ALL | |
| 009 | 20 | | PA | 24-0 | 21-45-11 | D04970J | | 3 | | | | SM00001 | | 9 | ALL | |
| 010 | 20 | | PA | 24-0 | 21-45-11 | D02966 | | 1 | | | | D03762 | 4 | | ALL | |
| 011 | 20 | | PA | 9-0 | 21-45-11 | D02966 | | 2 | | | | SM00001 | | 9 | ALL | |
| 012 | 20 | | PA | 5-0 | 21-45-11 | D02966 | | 3 | | | | GD00565 | S.. | 2 | ALL | |
| 013 | 20 | | PA | 27-0 | 21-45-11 | D02964 | | 1 | | | | D03762 | 10 | | ALL | |
| 014 | 20 | | PA | 12-0 | 21-45-11 | D02964 | | 2 | | | | SM00001 | | 9 | ALL | |
| 015 | 20 | | PA | 6-0 | 21-45-11 | D02964 | | 3 | | | | GD00561 | S.. | 2 | ALL | |
| 016 | 20 | | PA | 7-0 | 21-58-16 | D03058 | | 1 | | | | GD00595 | D.. | 2 | ALL | |
| 017 | 24 | | PK | 26-0 | 21-58-16 | D03058 | | 2 | | | | D04970J | 14 | | ALL | |
| 018 | 24 | | PK | 26-0 | 21-58-16 | D03058 | | 3 | | | | D04970J | 12 | | ALL | |
| 019 | 24 | | PK | 26-0 | 21-58-16 | D03058 | | 4 | | | | D04970J | 13 | | ALL | |
| 020 | 24 | | PK | 26-0 | 21-58-16 | D03058 | | 5 | | | | D04970J | 11 | | ALL | |
| 021 | 20 | | PA | 7-0 | 21-58-16 | D03058 | | 6 | | | | GD00595 | D.. | 2 | ALL | |
| 022 | 20 | | PA | 7-0 | 21-58-16 | D03058 | | 7 | | | | GD00595 | A.. | 2 | ALL | |
| 023 | 20 | | PA | 7-0 | 21-58-16 | D03058 | | 8 | | | | GD00595 | S.. | 2 | ALL | |
| 024 | 20 | | PA | 4-0 | 21-45-11 | D03762 | | 3 | | | | GD04510 | A.. | 2 | ALL | |
| 025 | 20 | | PA | 7-0 | 33-13-13 | D03762 | | 1 | | | | SP03778 | | W | 050-099 | |
| 025 | 20 | | PA | 8-0 | 33-13-13 | D03762 | | 1 | | | | SP03778 | | W | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0580

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0586 | 286T0586 | | | CO-PLT AUX HTR,R WINDSHIELD WIPER & RAIN REPELLANT (continued) | | | | | | | | | | | |
| 026 | 20 | | PA | | 5-0 | 33-13-13 | D03762 | | | | GD04510 | A.. | 2 | | ALL |
| 027 | 16 | | PA | | 24-0 | 30-42-11 | D04970J | | | | D04706J | | 4 | | ALL |
| 035 | 18 | | PA | | 24-0 | 30-42-11 | D04970J | | | 10 | D04706J | | 10 | | ALL |
| 037 | 20 | | PA | | 3-0 | SPARE | D04706J | | | | D06350J | | 2 | | ALL |
| 038 | 20 | | PA | | 24-0 | SPARE | D04970J | | CAP | Y | D06350J | | 3 | | ALL |
| 044 | 18 | | PA | | 7-0 | 33-13-13 | D06350J | | | | SP03778 | | | W | 050-099 |
| 044 | 18 | | PA | | 8-0 | 33-13-13 | D06350J | | | | SP03778 | | | W | 150-199, 275-299 |
| 045 | 18 | | PA | | 8-0 | 33-13-13 | SP03780 | | | | GD00073 | | A.. | 2 | 050-099, 150-156, 162-166, 275-276 |
| W0587 | 286T0587 | | | STAB TRIM CONTROL-LEFT | | | | | | | | | | | |
| 001 | 20 | | UA | | 26-2 | 27-41-11 | D02213 | | | | D04477J | | 1 | | 050-099, 155-199, 275-299 |
| 001 | 20 | | UA | | 27-0 | 27-41-11 | D00227 | | | | D04477J | | 1 | | 150-154 |
| 002 | 18 | | UA | | 2-10 | 27-41-11 | D02213 | | | | GD00297 | | D.. | N | 050-099, 155-199, 275-299 |
| 002 | 18 | | UA | | 3-0 | 27-41-11 | D00227 | | | | GD00297 | | D.. | N | 150-154 |
| 003Y | 18 | | XP | | 4-8 | 27-41-11 | D02207 | | | | GD00297 | | D.. | N | 050-099, 155-199, 275-299 |
| 003Y | 18 | | XP | | 5-0 | 27-41-11 | D00341 | | | | GD00297 | | D.. | N | 150-154 |
| 004Y | 20 | | XP | | 27-11 | 27-41-11 | D02207 | | | | D04477J | | 8 | | 050-099, 155-199, 275-299 |
| 004Y | 20 | | XP | | 27-0 | 27-41-11 | D00341 | | | | D04477J | | 8 | | 150-154 |
| 005Y | 20 | | XP | | 27-11 | 27-41-11 | D02207 | | | | D04477J | | 9 | | 050-099, 155-199, 275-299 |
| 005Y | 20 | | XP | | 27-0 | 27-41-11 | D00341 | | | | D04477J | | 9 | | 150-154 |
| 006Y | 18 | | XP | | 4-8 | 27-41-11 | D02207 | | | | GD00297 | | D.. | N | 050-099, 155-199, 275-299 |
| 006Y | 18 | | XP | | 5-0 | 27-41-11 | D00341 | | | | GD00297 | | D.. | N | 150-154 |
| 007Y | 18 | | XP | | 4-2 | 27-41-11 | D02207 | | | | GD00673 | | S.. | N | 050-099, 155-199, 275-299 |
| 007Y | 18 | | XP | | 5-0 | 27-41-11 | D00341 | | | | GD00673 | | S.. | N | 150-154 |
| 008Y | 20 | | XP | | 52-1 | 27-41-31 | D02207 | | | | D06027J | | 1 | | 050-099 |
| 008Y | 20 | | XP | | 52-7 | 27-41-31 | D02207 | | | | D06027J | | 1 | | 155-199, 275-299 |
| 009Y | 20 | | XP | | 52-1 | 27-41-31 | D02207 | | | | D06027J | | 2 | | 050-099 |
| 009Y | 20 | | XP | | 52-7 | 27-41-31 | D02207 | | | | D06027J | | 2 | | 155-199, 275-299 |
| 010Y | 18 | | XP | | 4-2 | 27-41-31 | D02207 | | | | GD00761 | | D.. | N | 050-099, 155-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0580
Page 10
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0587 | 286T0587 | | | STAB TRIM CONTROL-LEFT (continued) | | | | | | | | | | | | |
| 011Y | 18 | | XP | 4-2 | 27-41-31 | D02207 | | 7 | | GD00761 | D.. | N | | 050-099, 155-199, 275-299 | | |
| W0588 | 286T0588 | | | LDG GR SENSORS, HYD SYS R QTY & TEMP, REMOTE HYD QTY SEL & SW | | | | | | | | | | | | |
| 002 | 20 | PQ | P | 4-6 | 29-11-31 | GD00852 | | D.. | 2 | D05358J | | 2 | | ALL | | |
| 002Z | | | P | 0-0 | 29-11-31 | GD00852 | | DED | | D05358J | | DED | | ALL | | |
| 003 | | | R | 70-2 | 29-11-31 | D04934P | | | 3 | D05358J | | 3 | | 050-099 | | |
| 003 | 22 | PQ | R | 80-2 | 29-11-31 | D04934P | | | 3 | D05358J | | 3 | | 150-199, 275-299 | | |
| 003Z | | | R | 0-0 | 29-11-31 | D04934P | | DED | | D05358J | | DED | | ALL | | |
| 004 | 24 | PK | | 22-0 | 29-11-22 | D04934P | | | 5 | D05212J | | 5 | | ALL | | |
| 006 | 22 | PA | | 52-0 | 29-11-22 | D04934P | | | 6 | D05530J | | 2 | | 050-099 | | |
| 006 | 22 | PA | | 62-4 | 29-11-22 | D04934P | | | 6 | D05530J | | 2 | | 150-199, 275-299 | | |
| 007 | 24 | PK | | 52-0 | 29-11-22 | D04934P | | | 7 | D05530J | | 1 | | 050-099 | | |
| 007 | 24 | PK | | 62-4 | 29-11-22 | D04934P | | | 7 | D05530J | | 1 | | 150-199, 275-299 | | |
| 008 | 22 | PA | | 52-0 | 29-11-22 | D04934P | | | 8 | D05530J | | 5 | | 050-099 | | |
| 008 | 22 | PA | | 62-4 | 29-11-22 | D04934P | | | 8 | D05530J | | 5 | | 150-199, 275-299 | | |
| 013 | 18 | PA | | 2-0 | 29-33-11 | D02220 | | | 1 | D02218 | | 3 | | ALL | | |
| 014 | 18 | PA | | 9-2 | 29-33-11 | D02220 | | | 3 | GD00028 | S.. | 2 | | ALL | | |
| 015 | 18 | PA | | 92-0 | 29-33-11 | D02220 | | | 2 | D05212J | | 2 | DL | 050-099 | | |
| 015 | 18 | PA | | 102-1 | 29-33-11 | D02220 | | | 2 | D05212J | | 2 | DL | 150-199, 275-299 | | |
| 016 | 20 | PA | | 92-0 | 29-33-11 | D05212J | | | 6 | D02218 | | 5 | | 050-099 | | |
| 016 | 20 | PA | | 102-0 | 29-33-11 | D05212J | | | 6 | D02218 | | 5 | | 150-199, 275-299 | | |
| 017 | 20 | PA | | 92-0 | 29-33-11 | D05212J | | | 7 | D02218 | | 6 | | 050-099 | | |
| 017 | 20 | PA | | 102-0 | 29-33-11 | D05212J | | | 7 | D02218 | | 6 | | 150-199, 275-299 | | |
| 018 | 20 | PA | | 92-0 | 29-33-11 | D05212J | | | 8 | D02218 | | 2 | | 050-099 | | |
| 018 | 20 | PA | | 102-0 | 29-33-11 | D05212J | | | 8 | D02218 | | 2 | | 150-199, 275-299 | | |
| 019 | 22 | PA | | 48-9 | SPARE | D05212J | | | 14 | D08066J | | 7 | | 050-099 | | |
| 019 | 22 | PA | | 59-7 | SPARE | D05212J | | | 14 | D08066J | | 7 | | 150-199, 275-299 | | |
| 021 | 24 | PK | | 52-2 | 21-53-22 | D04934P | | | 10 | D08066J | | 1 | | 050-099 | | |
| 021 | 24 | PK | | 62-6 | 21-53-22 | D04934P | | | 10 | D08066J | | 1 | | 150-199, 275-299 | | |
| 022 | 24 | PK | | 52-2 | 21-53-22 | D04934P | | | 11 | D08066J | | 2 | | 050-099 | | |
| 022 | 24 | PK | | 62-6 | 21-53-22 | D04934P | | | 11 | D08066J | | 2 | | 150-199, 275-299 | | |
| 023 | 24 | PK | | 52-2 | 21-53-22 | D04934P | | | 12 | D08066J | | 3 | | 050-099 | | |
| 023 | 24 | PK | | 62-6 | 21-53-22 | D04934P | | | 12 | D08066J | | 3 | | 150-199, 275-299 | | |
| 024 | 24 | PK | | 52-2 | 21-53-22 | D04934P | | | 13 | D08066J | | 4 | | 050-099 | | |
| 024 | 24 | PK | | 62-6 | 21-53-22 | D04934P | | | 13 | D08066J | | 4 | | 150-199, 275-299 | | |
| 025 | 24 | PK | | 52-2 | 21-53-22 | D04934P | | | 14 | D08066J | | 5 | | 050-099 | | |
| 025 | 24 | PK | | 62-6 | 21-53-22 | D04934P | | | 14 | D08066J | | 5 | | 150-199, 275-299 | | |
| 026 | 24 | PK | | 52-2 | 21-53-22 | D04934P | | | 16 | D08066J | | 6 | | 050-099 | | |

WIRE LIST

D280T132

91-21-11

Section W0580

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | | |
|------------------------|-----------------|----|------|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0588 | 286T0588 | | | LDG GR SENSORS, HYD SYS R QTY & TEMP, REMOTE HYD QTY SEL & SW (continued) | | | | | | | | | | | | | | | |
| 026 | 24 | | PK | 62-6 | 21-53-22 | D04934P | | 16 | | | | | | D08066J | | 6 | | | 150-199, 275-299 |
| 027 | 24 | | PK | 15-2 | 21-31-21 | D05544J | | 11 | | | | | | D05212J | | 9 | | | ALL |
| 031 | 18 | | PA | 9-1 | 29-33-11 | D02218 | | 4 | | | | | | GD00028 | S.. | 2 | | | 050-099 |
| 031 | 18 | | PA | 9-2 | 29-33-11 | D02218 | | 4 | | | | | | GD00028 | S.. | 2 | | | 150-199, 275-299 |
| 032 | 24 | | PK | 21-3 | 27-51-61 | D04934P | | 25 | | | | | | D05288J | | 7 | | | ALL |
| 033 | 24 | | PK | 21-3 | 27-51-61 | D04934P | | 31 | | | | | | D05288J | | 8 | | | ALL |
| 034 | 24 | | PK | 21-3 | 27-51-61 | D04934P | | 9 | | | | | | D05288J | | 9 | | | 050-099 |
| 035 | 22 | | PA | 52-0 | SPARE | D04934P | | 21 | | | | | | D05530J | | 8 | | | 050-099 |
| 035 | 22 | | PA | 62-4 | SPARE | D04934P | | 21 | | | | | | D05530J | | 8 | | | 150-199, 275-299 |
| 036 | 20 | | PA | 67-6 | SPARE | D04936J | | 12 | | | | | | D05516J | | 3 | | | 050-099 |
| 036 | 20 | | PA | 77-6 | SPARE | D04936J | | 12 | | | | | | D05516J | | 3 | | | 150-199, 275-299 |
| 040R | 22 | | PH | 52-2 | 26-18-21 | D04934P | | 15 | | | | | | D08066J | | 8 | | | 050-099 |
| 040R | 22 | | PH | 62-6 | 26-18-21 | D04934P | | 15 | | | | | | D08066J | | 8 | | | 150-199, 275-299 |
| 043 | 24 | | PK | 48-6 | 29-11-22 | D05212J | | 1 | | | | | | D05530J | | 6 | | | 050-099 |
| 043 | 24 | | PK | 59-4 | 29-11-22 | D05212J | | 1 | | | | | | D05530J | | 6 | | | 150-199, 275-299 |
| 045 | 22 | | PA | 3-10 | 29-11-22 | GD03558 | | | D.. | 2 | | | | D05530J | | 3 | | | ALL |
| 048 | 20 | | PA | 4-6 | 29-11-31 | GD00852 | | | D.. | 2 | | | | D05358J | | 7 | | | ALL |
| 049 | 22 | | PA | 23-3 | 78-36-11 | D05544J | | 19 | | | | | | D04934P | | 26 | | | ALL |
| 057 | 22 | | PA | 23-3 | 27-89-11 | D04934P | | 27 | | | | | | D05544J | | 3 | | | ALL |
| 058 | 22 | | PA | 23-3 | 27-89-11 | D04934P | | 28 | | | | | | D05544J | | 4 | | | ALL |
| 059 | 22 | | PA | 23-3 | 27-89-11 | D04934P | | 29 | | | | | | D05544J | | 17 | | | ALL |
| 060 | 22 | | PA | 23-3 | 27-89-11 | D04934P | | 30 | | | | | | D05544J | | 18 | | | ALL |
| 201B | 22 | | PB A | 68-8 | 32-61-12 | D05544J | | 2 | | | | | | D05516J | | 2 | | | 050-099 |
| 201B | 22 | | PB A | 78-8 | 32-61-12 | D05544J | | 2 | | | | | | D05516J | | 2 | | | 150-199, 275-299 |
| 201R | 22 | | PB A | 0-0 | 32-61-12 | D05544J | | 1 | | | | | | D05516J | | 1 | | | ALL |
| 203B | 22 | | PB C | 68-7 | 32-61-12 | D05544J | | 6 | | | | | | D04300J | | 2 | | | 050-099 |
| 203B | 22 | | PB C | 78-7 | 32-61-12 | D05544J | | 6 | | | | | | D04300J | | 2 | | | 150-199, 275-299 |
| 203R | 22 | | PB C | 0-0 | 32-61-12 | D05544J | | 5 | | | | | | D04300J | | 1 | | | ALL |
| 204B | 22 | | PB D | 68-7 | 32-61-12 | D05544J | | 8 | | | | | | D04300J | | 4 | | | 050-099 |
| 204B | 22 | | PB D | 78-7 | 32-61-12 | D05544J | | 8 | | | | | | D04300J | | 4 | | | 150-199, 275-299 |
| 204R | 22 | | PB D | 0-0 | 32-61-12 | D05544J | | 7 | | | | | | D04300J | | 3 | | | ALL |
| 205B | 22 | | PB E | 68-7 | 32-09-11 | D05544J | | 10 | | | | | | D04300J | | 6 | | | 050-099 |
| 205B | 22 | | PB E | 78-7 | 32-09-11 | D05544J | | 10 | | | | | | D04300J | | 6 | | | 150-199, 275-299 |
| 205R | 22 | | PB E | 0-0 | 32-09-11 | D05544J | | 9 | | | | | | D04300J | | 5 | | | ALL |
| 206B | 20 | | PR F | 67-5 | 32-42-11 | D04936J | | 8 | | | | | | D04300J | | 8 | | | 050-099 |
| 206B | 20 | | PR F | 77-5 | 32-42-11 | D04936J | | 8 | | | | | | D04300J | | 8 | | | 150-199, 275-299 |
| 206R | 20 | | PR F | 0-0 | 32-42-11 | D04936J | | 7 | | | | | | D04300J | | 7 | | | ALL |
| 206Z | | | F | 0-0 | 32-42-11 | D04936J | | 6 | | | | | | D04300J | | 17 | | | ALL |
| 207B | 20 | | PR G | 67-5 | 32-42-11 | D04936J | | 10 | | | | | | D04300J | | 10 | | | 050-099 |

WIRE LIST

D280T132

91-21-11
Section W0580
Page 12
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-------|--|---------|-------|------|------|--------|-------|---------|------|--------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0588 | 286T0588 | | | | LDG GR SENSORS, HYD SYS R QTY & TEMP, REMOTE HYD QTY SEL & SW (continued) | | | | | | | | | | | |
| 207B | 20 | PR | G | 77-5 | 32-42-11 | D04936J | | 10 | | | | D04300J | 10 | | | 150-199, 275-299 |
| 207R | 20 | PR | G | 0-0 | 32-42-11 | D04936J | | 9 | | | | D04300J | 9 | | | ALL |
| 207Z | | | G | 0-0 | 32-42-11 | D04936J | | 11 | | | | D04300J | 19 | | | ALL |
| 209B | 24 | PL | L | 15-2 | 21-31-21 | D05544J | | 12 | | | | D05212J | 10 | | | ALL |
| 209R | 24 | PL | L | 0-0 | 21-31-21 | D05544J | | 13 | | | | D05212J | 11 | | | ALL |
| 210B | 24 | PL | M | 15-2 | 21-31-21 | D05544J | | 14 | | | | D05212J | 12 | | | ALL |
| 210R | 24 | PL | M | 0-0 | 21-31-21 | D05544J | | 15 | | | | D05212J | 13 | | | ALL |
| 211B | 22 | PB | B | 52-2 | 21-51-23 | D08066J | | 13 | | | | D04934P | 4 | | | 050-099 |
| 211B | 22 | PB | B | 62-6 | 21-51-23 | D08066J | | 13 | | | | D04934P | 4 | | | 150-199, 275-299 |
| 211R | 22 | PB | B | 0-0 | 21-51-23 | D08066J | | 14 | | | | D04934P | 20 | | | ALL |
| 212B | 22 | PB | K | 52-2 | 21-51-23 | D08066J | | 15 | | | | D04934P | 23 | | | 050-099 |
| 212B | 22 | PB | K | 62-6 | 21-51-23 | D08066J | | 15 | | | | D04934P | 23 | | | 150-199, 275-299 |
| 212R | 22 | PB | K | 0-0 | 21-51-23 | D08066J | | 16 | | | | D04934P | 24 | | | ALL |
| 213B | 20 | PR | N | 66-6 | 29-11-31 | D05288J | | 5 | | | | D05358J | 1 | | | 050-099 |
| 213B | 20 | PR | N | 76-6 | 29-11-31 | D05288J | | 5 | | | | D05358J | 1 | | | 150-199, 275-299 |
| 213R | 20 | PR | N | 0-0 | 29-11-31 | D05288J | | 6 | | | | D05358J | 4 | | | ALL |
| 213Z | | | N | 0-0 | 29-11-31 | D05288J | | DED | | | | D05358J | DED | | | ALL |
| 239B | 24 | PL | JN | 106-2 | 21-51-12 | D04934P | | 18 | | | | D05904J | 4 | | | 050-099 |
| 239B | 24 | PL | JN | 127-1 | 21-51-12 | D04934P | | 18 | | | | D05904J | 4 | | | 150-199, 275-299 |
| 239R | 24 | PL | JN | 0-0 | 21-51-12 | D04934P | | 17 | | | | D05904J | 3 | | | ALL |
| 451G | 22 | XU | H | 66-7 | 32-46-11 | D05288J | | 2 | 4F | | | D04300J | 12 | 4H | | 050-099 |
| 451G | 22 | XU | H | 76-7 | 32-46-11 | D05288J | | 2 | 4F | | | D04300J | 12 | 4H | | 150-199, 275-299 |
| 451W | 22 | XU | H | 0-0 | 32-46-11 | D05288J | | 1 | 4J | | | D04300J | 11 | 4L | | ALL |
| 452G | 22 | XU | J | 66-7 | 32-46-11 | D05288J | | 4 | 4F | | | D04300J | 14 | 4H | | 050-099 |
| 452G | 22 | XU | J | 76-7 | 32-46-11 | D05288J | | 4 | 4F | | | D04300J | 14 | 4H | | 150-199, 275-299 |
| 452W | 22 | XU | J | 0-0 | 32-46-11 | D05288J | | 3 | 4J | | | D04300J | 13 | 4L | | ALL |
| W0589 | 286T0589 | | | | STAB TRIM CONTROL-RIGHT | | | | | | | | | | | |
| 001 | 20 | UA | | 27-0 | 27-41-21 | D02221 | | 1 | | | | D04479J | 1 | | | 050-099 |
| 001 | 20 | UA | | 27-0 | 27-41-21 | D00241 | | 1 | | | | D04479J | 1 | | | 150-154 |
| 001 | 20 | UA | | 26-3 | 27-41-21 | D02221 | | 1 | | | | D04479J | 1 | | | 155-199, 275-299 |
| 002 | 18 | UA | | 5-0 | 27-41-21 | D02221 | | 2 | DK | | | GD00289 | D.. | N | | 050-099 |
| 002 | 18 | UA | | 5-0 | 27-41-21 | D00241 | | 2 | DK | | | GD00289 | D.. | N | | 150-154 |
| 002 | 18 | UA | | 3-8 | 27-41-21 | D02221 | | 2 | DK | | | GD00289 | D.. | N | | 155-199, 275-299 |
| 003Y | 18 | XP | | 4-0 | 27-41-21 | D02215 | | 5 | | | | GD00289 | D.. | N | | 050-099 |
| 003Y | 18 | XP | | 5-0 | 27-41-21 | D00345 | | 7 | DK | | | GD00289 | D.. | N | | 150-154 |
| 003Y | 18 | XP | | 3-7 | 27-41-21 | D02215 | | 5 | | | | GD00289 | D.. | N | | 155-199, 275-299 |
| 004Y | 20 | XP | | 27-0 | 27-41-21 | D02215 | | 6 | | | | D04479J | 8 | | | 050-099 |
| 004Y | 20 | XP | | 27-0 | 27-41-21 | D00345 | | 8 | | | | D04479J | 8 | | | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0580

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0589 | 286T0589 | | | STAB TRIM CONTROL-RIGHT (continued) | | | | | | | | | | | |
| 004Y | 20 | | XP | | 26-5 | 27-41-21 | D02215 | | | | D04479J | | 8 | | 155-199, 275-299 |
| 005Y | 20 | | XP | | 27-0 | 27-41-21 | D02215 | | | | D04479J | | 9 | | 050-099 |
| 005Y | 20 | | XP | | 27-0 | 27-41-21 | D00345 | | | 13 | D04479J | | 9 | | 150-154 |
| 005Y | 20 | | XP | | 26-5 | 27-41-21 | D02215 | | | 2 | D04479J | | 9 | | 155-199, 275-299 |
| 006Y | 18 | | XP | | 4-0 | 27-41-21 | D02215 | | | 1 | GD00289 | D.. | N | | 050-099 |
| 006Y | 18 | | XP | | 5-0 | 27-41-21 | D00345 | | | 12 | GD00289 | D.. | N | | 150-154 |
| 006Y | 18 | | XP | | 3-7 | 27-41-21 | D02215 | | | 1 | GD00289 | D.. | N | | 155-199, 275-299 |
| 007Y | 18 | | XP | | 4-0 | 27-41-21 | D02215 | | | 10 | GD00677 | S.. | N | | 050-099 |
| 007Y | 18 | | XP | | 6-0 | 27-41-21 | D00345 | | | 6 | GD00677 | S.. | N | | 150-154 |
| 007Y | 18 | | XP | | 3-7 | 27-41-21 | D02215 | | | 10 | GD00677 | S.. | N | | 155-199, 275-299 |
| 008Y | 20 | | XP | | 41-0 | 27-41-31 | D02215 | | | 8 | D06025J | | 1 | | 050-099 |
| 008Y | 20 | | XP | | 40-9 | 27-41-31 | D02215 | | | 8 | D06025J | | 1 | | 155-199, 275-299 |
| 009Y | 20 | | XP | | 41-0 | 27-41-31 | D02215 | | | 4 | D06025J | | 2 | | 050-099 |
| 009Y | 20 | | XP | | 40-9 | 27-41-31 | D02215 | | | 4 | D06025J | | 2 | | 155-199, 275-299 |
| 010Y | 18 | | XP | | 4-0 | 27-41-31 | D02215 | | | 3 | GD00759 | D.. | N | | 050-099 |
| 010Y | 18 | | XP | | 3-8 | 27-41-31 | D02215 | | | 3 | GD00759 | D.. | N | | 155-199, 275-299 |
| 011Y | 18 | | XP | | 4-0 | 27-41-31 | D02215 | | | 7 | GD00759 | D.. | N | | 050-099 |
| 011Y | 18 | | XP | | 3-8 | 27-41-31 | D02215 | | | 7 | GD00759 | D.. | N | | 155-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0580
Page 14 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|-----|----|--|-----------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0590 | 286T0590 | | | AIR HYD PUMP CONTROL & INDICATION | | | | | | | | | | | | | | | |
| 001 | 22 | | PA | | 32-2 | 32-41-11 | D04854P | | | | 3 | | | D04856P | | 3 | | | ALL |
| 002 | 24 | | PK | | 17-10 | 29-21-31 | D05052P | | | | 15 | | | SM00001 | | | 9 | | ALL |
| 004 | 24 | | PK | | 32-7 | 29-21-31 | D10434 | | | | 4 | | | D04856P | | 12 | | | ALL |
| 005 | 20 | | PA | | 32-2 | 28-22-31 | D04854P | | | | 5 | | | D04856P | | 5 | | | ALL |
| 006 | 20 | | PA | | 32-2 | 28-22-31 | D04854P | | | | 9 | | | D04856P | | 6 | | | ALL |
| 007 | 18 | | PA | | 94-4 | 28-25-21 | SP02294 | | | | | 9 | | D05698J | | 7 | | | 050-099 |
| 007 | 18 | | PA | | 105-0 | 28-25-21 | SP02294 | | | | | 9 | | D05698J | | 7 | | | 150-199, 275-299 |
| 009 | 18 | | PA | | 32-2 | 28-22-31 | D04854P | | | | 4 | | | D04856P | | 18 | DK | | 050-099, 150-199, 275-278 |
| 009 | 18 | | PA | | 32-2 | 28-22-31 | D04854P | | | | 4 | | | D04856P | | 18 | DL | | 280-299 |
| 010 | 20 | | PA | | 13-7 | 28-26-11 | D04860P | | | | 10 | | | D04856P | | 30 | | | ALL |
| 011 | 18 | | PA | | 32-2 | 28-26-11 | D04854P | | | | 2 | | | D04856P | | 31 | | | ALL |
| 012 | 18 | | PA | | 32-2 | SPARE | D04854P | | | | 27 | DL | | D04856P | | 42 | | | 150-154 |
| 012 | 18 | | PA | | 13-7 | 38-32-11 | D04860P | | | | 9 | DL | | D04856P | | 42 | | | 156-157, 166-199, 275-299 |
| 013 | 20 | | PA | | 23-7 | SPARE | D04854P | | | | 16 | | | D04860P | | 5 | | | ALL |
| 015 | 20 | | PA | | 32-2 | SPARE | D04854P | | | | 11 | | | D04856P | | 17 | | | ALL |
| 016 | 22 | | PA | | 13-7 | 28-21-11 | D04860P | | | | 4 | | | D04856P | | 15 | | | ALL |
| 017 | 18 | | PA | | 32-2 | 28-21-11 | D04854P | | | | 10 | | | D04856P | | 27 | | | ALL |
| 018 | 24 | | PK | | 18-5 | 36-11-61 | D05052P | | | | 30 | | | D04856P | | 25 | | | 050-099, 155-156, 162-166 |
| 018 | 24 | | PK | | 18-5 | SPARE | D05052P | | | | 30 | | | D04856P | | 25 | | | 150-154, 157, 167-199, 275-299 |
| 019 | 22 | | PA | | 13-7 | 28-41-12 | D04860P | | | | 7 | | | D04856P | | 40 | | | ALL |
| 020 | 18 | | PA | | 32-2 | 28-41-12 | D04854P | | | | 8 | | | D04856P | | 41 | | | ALL |
| 021 | 24 | | PV | AU | 25-0 | 28-22-12 | D04856P | | | | 13 | | | D05052P | | 12 | | | 150-199 |
| 021Z | | | | AU | 0-0 | 28-22-12 | D04856P | | | | DED | | | D05052P | | DED | | | 150-199 |
| 022 | 24 | | PK | | 18-5 | 29-21-31 | D04856P | | | | 24 | | | D05052P | | 27 | | | ALL |
| 023 | 22 | | PA | | 32-2 | 29-11-32 | D04854P | | | | 23 | | | D04856P | | 23 | | | ALL |
| 026 | 22 | | PA | | 32-2 | 29-11-32 | D04854P | | | | 26 | | | D04856P | | 26 | | | ALL |
| 027 | 22 | | PA | | 17-9 | 29-11-32 | D04854P | | | | 19 | | | D05052P | | 7 | | | ALL |
| 028 | 20 | | PA | | 7-1 | 29-21-31 | D10434 | | | | 2 | | | GD00595 | | D.. | 2 | | ALL |
| 029 | 24 | | PK | | 17-9 | 28-25-11 | D05052P | | | | 32 | | | D04854P | | 29 | | | ALL |
| 030 | 24 | | PK | | 17-9 | 28-25-11 | D05052P | | | | 31 | | | D04854P | | 28 | | | ALL |
| 031 | 24 | | PK | | 0-11 | 29-21-31 | D10434 | | | | 3 | | | SM00001 | | | 9 | | ALL |
| 032 | 24 | | PK | | 0-11 | 29-21-31 | D10434 | | | | 1 | | | SM00001 | | | 9 | | ALL |
| 033 | 18 | | PA | | 48-1 | 28-21-13 | SP01530 | | | | | S | | D05698J | | 4 | | | 050-099 |
| 033 | 18 | | PA | | 48-11 | 28-21-13 | SP01530 | | | | | S | | D05698J | | 4 | | | 150-199, 275-299 |
| 034 | 18 | | PA | | 48-1 | 28-21-13 | SP01532 | | | | | S | | D05698J | | 5 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 1

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|---------|------|------|------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0590 | 286T0590 | | | AIR HYD PUMP CONTROL & INDICATION (continued) | | | | | | | | | | | |
| 034 | 18 | PA | | 48-11 | 28-21-13 | SP01532 | | S | | D05698J | 5 | | | 150-199, 275-299 | |
| 035 | 22 | PA | | 13-7 | 28-21-13 | D04860P | | | 2 | D04856P | 33 | | | ALL | |
| 036 | 20 | PA | | 32-2 | 28-21-13 | D04854P | | | 17 | D04856P | 1 | | | ALL | |
| 037 | 14 | PQ | A | 91-1 | 28-25-11 | D05052P | | | 1 | D05698J | 6 | | | 050-099 | |
| 037 | 12 | PQ | A | 101-9 | 28-25-11 | D05052P | | | 1 | D05698J | 6 | | | 150-199, 275-299 | |
| 037Z | | | A | 0-0 | 28-25-11 | D05052P | | | 5 | D05698J | | | FA | ALL | |
| 038 | 16 | PA | | 17-9 | 28-25-11 | D04854P | | | 1 | D05052P | 2 | | | 050-099 | |
| 038 | 12 | PA | | 17-9 | 28-25-11 | D04854P | | | 1 | D05052P | 2 | | | 150-199, 275-299 | |
| 040 | 18 | PA | | 32-2 | 28-41-12 | D04854P | | | 6 | D04856P | 28 | | | ALL | |
| 044 | 16 | PA | | 18-5 | 27-09-13 | D04856P | | | 29 | D05052P | 4 | | | ALL | |
| 045 | 20 | UA | | 4-3 | 28-25-11 | D05698J | | | | FA | GD00788 | S.. | 2 | 050-099 | |
| 045 | 20 | UA | | 5-1 | 28-25-11 | D05698J | | | | FA | GD00788 | S.. | 2 | 150-199, 275-299 | |
| 046 | 24 | PK | | 18-5 | 28-22-12 | D04856P | | | 22 | D05052P | 23 | | | ALL | |
| 051 | 24 | PK | | 12-7 | 21-33-21 | D04854P | | | 24 | D10192 | 1 | | | ALL | |
| 052 | 24 | PK | | 12-7 | 21-33-21 | D04854P | | | 25 | D10192 | 2 | | | ALL | |
| 053 | 24 | PK | | 12-7 | 21-33-21 | D04854P | | | 12 | D10192 | 3 | | | ALL | |
| 054 | 24 | PK | | 12-7 | 21-33-21 | D04854P | | | 13 | D10192 | 4 | | | ALL | |
| 055 | 24 | PK | | 18-5 | 28-22-11 | D04856P | | | 10 | D05052P | 17 | | | ALL | |
| 056 | 24 | PK | | 18-5 | 28-25-11 | D04856P | | | 16 | D05052P | 18 | | | ALL | |
| 059 | 24 | PK | | 17-9 | 28-25-11 | D04854P | | | 30 | D05052P | 21 | | | ALL | |
| 061 | 20 | PA | | 6-2 | 21-33-21 | GD00595 | | | S.. | 2 | D10192 | 5 | | ALL | |
| 062 | 22 | PA | | 32-2 | SPARE | D04854P | | | 18 | D04856P | 8 | | | 150-154, 275 | |
| 065 | 22 | PA | | 32-2 | 29-11-32 | D04854P | | | 15 | D04856P | 34 | | | ALL | |
| 066 | 22 | PA | | 32-2 | 29-11-32 | D04854P | | | 22 | D04856P | 35 | | | ALL | |
| 067 | 22 | PA | | 32-2 | 29-11-32 | D04854P | | | 32 | D04856P | 36 | | | ALL | |
| 069 | 22 | PA | | 32-2 | 28-22-31 | D04854P | | | 31 | D04856P | 19 | | | ALL | |
| 070 | 18 | PA | | 18-5 | 27-11-12 | D05052P | | | 24 | DL | D04856P | 32 | | ALL | |
| 071 | 18 | PA | | 18-5 | 27-11-12 | D05052P | | | 25 | DL | D04856P | 37 | | ALL | |
| 072 | 20 | PA | | 18-5 | 27-11-12 | D05052P | | | 26 | | D04856P | 38 | | ALL | |
| 073 | 20 | PA | | 18-5 | 27-11-12 | D05052P | | | 28 | | D04856P | 39 | | ALL | |
| 074R | 22 | PH | | 18-5 | 26-17-11 | D05052P | | | 11 | | D04856P | 21 | | ALL | |
| 075 | 24 | PK | | 17-9 | 29-11-32 | D04854P | | | 7 | | D05052P | 9 | | ALL | |
| 088 | 22 | PA | | 18-5 | 28-31-12 | D04856P | | | 4 | | D05052P | 6 | | 050-099, 155-199, 276-299 | |
| 089 | 22 | PA | | 18-5 | 28-42-13 | D04856P | | | 8 | | D05052P | 10 | | 050-099, 155-199, 276-299 | |
| 801 | 20 | PA | | 32-2 | SPARE | D04854P | | | 21 | | D04856P | 43 | | 150-154 | |
| 801 | 18 | PA | | 13-7 | 38-32-11 | D04860P | | | 8 | DL | D04856P | 43 | | 156-157, 166-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 2

Feb 06/2009



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0590 | 286T0590 | | | AIR HYD PUMP CONTROL & INDICATION (continued) | | | | | | | | | | | | |
| 801 | 20 | PA | | 13-7 | 38-32-11 | D04860P | | 8 | | | D04856P | | 43 | | 275-276 | |
| W0591 | 286T0591 | | | PITCH SERVO ACTR | | | | | | | | | | | | |
| 001 | 20 | UA | | 32-8 | 22-11-12 | D00181 | | 2 | | | D04475J | | 1 | | ALL | |
| 002 | 20 | UA | | 32-8 | 22-11-12 | D00181 | | 18 | | | D04475J | | 14 | | ALL | |
| 003 | 18 | UA | | 3-7 | 22-11-12 | D00181 | | 17 | | | GD00129 | D.. | N | | ALL | |
| 004 | 18 | UA | | 3-7 | 22-11-12 | D00181 | | 1 | | | GD00129 | D.. | N | | ALL | |
| 005 | 18 | UA | | 3-8 | 22-11-12 | D00181 | | 19 | | | GD00131 | S.. | N | | ALL | |
| 006 | 16 | UA | | 36-2 | 27-32-31 | D04475J | | 20 | FL | | D01721 | | 2 | | ALL | |
| 007 | 16 | UA | | 36-2 | 27-32-31 | D04475J | | 24 | FL | | D01721 | | 1 | | ALL | |
| 008 | 16 | UA | | 7-8 | 27-32-31 | GD00129 | | D.. | N | | D01721 | | 3 | | ALL | |
| 009 | 16 | UA | | 7-8 | 27-32-31 | GD00129 | | D.. | N | | D01721 | | 4 | | ALL | |
| 010Y | 20 | XP | | 4-7 | 27-41-11 | D04475J | | 3 | | | SP00391 | | 9 | | ALL | |
| 201B | 20 | UB | IA | 32-8 | 22-11-11 | D04475J | | 5 | | | SM00002 | | 9 | | ALL | |
| 201R | 20 | UB | IA | 0-0 | 22-11-11 | D04475J | | 4 | | | SM00001 | | 9 | | ALL | |
| 203B | 20 | UB | IC | 2-0 | 22-11-11 | D00181 | | 7 | | | SM00002 | | 9 | | ALL | |
| 203R | 20 | UB | IC | 0-0 | 22-11-11 | D00181 | | 8 | | | SM00001 | | 9 | | ALL | |
| 204B | 20 | UB | ID | 2-0 | 22-11-11 | D00181 | | 12 | | | SM00002 | | 9 | | ALL | |
| 204R | 20 | UB | ID | 0-0 | 22-11-11 | D00181 | | 13 | | | SM00001 | | 9 | | ALL | |
| 207B | 20 | UB | IG | 32-8 | 22-12-11 | D04475J | | 10 | | | SM00006 | | 9 | | ALL | |
| 207R | 20 | UB | IG | 0-0 | 22-12-11 | D04475J | | 9 | | | SM00005 | | 9 | | ALL | |
| 208B | 20 | UB | IH | 2-0 | 22-12-11 | D00181 | | 3 | | | SM00006 | | 9 | | ALL | |
| 208R | 20 | UB | IH | 0-0 | 22-12-11 | D00181 | | 4 | | | SM00005 | | 9 | | ALL | |
| 209B | 20 | UB | II | 2-0 | 22-12-11 | D00181 | | 5 | | | SM00006 | | 9 | | ALL | |
| 209R | 20 | UB | II | 0-0 | 22-12-11 | D00181 | | 6 | | | SM00005 | | 9 | | ALL | |
| 301B | 20 | UC | MA | 32-8 | 22-12-11 | D04475J | | 12 | | | D00181 | | 15 | | ALL | |
| 301R | 20 | UC | MA | 0-0 | 22-12-11 | D04475J | | 11 | | | D00181 | | 14 | | ALL | |
| 301Y | 20 | UC | MA | 0-0 | 22-12-11 | D04475J | | 13 | | | D00181 | | 16 | | ALL | |
| 302B | 20 | UC | MB | 32-8 | 22-12-11 | D04475J | | 7 | | | D00181 | | 10 | | ALL | |
| 302R | 20 | UC | MB | 0-0 | 22-12-11 | D04475J | | 6 | | | D00181 | | 9 | | ALL | |
| 302Y | 20 | UC | MB | 0-0 | 22-12-11 | D04475J | | 8 | | | D00181 | | 11 | | ALL | |
| 70M | 18 | 5A | | 2-4 | 29-11-14 | D02089 | | 1 | | | GD00757 | D.. | N | | ALL | |
| 70N | 18 | 5A | | 23-4 | 29-11-14 | D02089 | | 3 | | | D04475J | | 22 | DL | ALL | |
| 70P | 18 | 5A | | 23-4 | 29-11-14 | D02089 | | 2 | | | D04475J | | 23 | DL | ALL | |
| W0593 | 286T0593 | | | RO SERVO ACTR L | | | | | | | | | | | | |
| 006 | 20 | UA | | 27-6 | 22-11-12 | D00179 | | 2 | | | D04519J | | 3 | | ALL | |
| 007 | 20 | UA | | 27-6 | 22-11-12 | D00179 | | 18 | | | D04519J | | 9 | | ALL | |
| 008 | 18 | UA | | 2-1 | 22-11-12 | D00179 | | 17 | | | GD00133 | D.. | N | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 3

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|-------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0593 | 286T0593 | | | RO SERVO ACTR L (continued) | | | | | | | | | | | |
| 009 | 18 | | UA | | 2-1 | 22-11-12 | D00179 | | 1 | | GD00133 | D.. | N | | ALL |
| 010 | 18 | | UA | | 2-2 | 22-11-12 | D00179 | | 19 | | GD00135 | S.. | N | | ALL |
| 011 | 18 | | UA | | 4-5 | 27-21-11 | D04519J | | 5 | DL | SP00752 | | 9 | | ALL |
| 202B | 20 | | UB | IB | 0-7 | 22-11-11 | D04519J | | 8 | | SM00004 | | 9 | | ALL |
| 202R | 20 | | UB | IB | 0-0 | 22-11-11 | D04519J | | 7 | | SM00003 | | 9 | | ALL |
| 205B | 20 | | UB | IE | 27-6 | 22-11-11 | D00179 | | 7 | | SM00004 | | 9 | | ALL |
| 205R | 20 | | UB | IE | 0-0 | 22-11-11 | D00179 | | 8 | | SM00003 | | 9 | | ALL |
| 206B | 20 | | UB | IF | 27-6 | 22-11-11 | D00179 | | 12 | | SM00004 | | 9 | | ALL |
| 206R | 20 | | UB | IF | 0-0 | 22-11-11 | D00179 | | 13 | | SM00003 | | 9 | | ALL |
| 210B | 20 | | UB | IJ | 1-0 | 22-13-11 | D04519J | | 2 | | SM00008 | | 9 | | ALL |
| 210R | 20 | | UB | IJ | 0-0 | 22-13-11 | D04519J | | 1 | | SM00007 | | 9 | | ALL |
| 211B | 20 | | UB | IK | 29-0 | 22-13-11 | D00179 | | 6 | | SM00008 | | 9 | | ALL |
| 211R | 20 | | UB | IK | 0-0 | 22-13-11 | D00179 | | 5 | | SM00007 | | 9 | | ALL |
| 212B | 20 | | UB | IL | 29-0 | 22-13-11 | D00179 | | 4 | | SM00008 | | 9 | | ALL |
| 212R | 20 | | UB | IL | 0-0 | 22-13-11 | D00179 | | 3 | | SM00007 | | 9 | | ALL |
| 303B | 20 | | UC | MC | 27-6 | 22-13-11 | D00179 | | 15 | | D04519J | | 11 | | ALL |
| 303R | 20 | | UC | MC | 0-0 | 22-13-11 | D00179 | | 16 | | D04519J | | 10 | | ALL |
| 303Y | 20 | | UC | MC | 0-0 | 22-13-11 | D00179 | | 14 | | D04519J | | 12 | | ALL |
| 304B | 20 | | UC | MD | 27-6 | 22-13-11 | D00179 | | 10 | | D04519J | | 14 | | ALL |
| 304R | 20 | | UC | MD | 0-0 | 22-13-11 | D00179 | | 11 | | D04519J | | 13 | | ALL |
| 304Y | 20 | | UC | MD | 0-0 | 22-13-11 | D00179 | | 9 | | D04519J | | 15 | | ALL |
| W0596 | 286T0596 | | | FUELING CONTROL & DEFUELING VALVES | | | | | | | | | | | |
| 001 | 22 | | PA | | 75-3 | 28-42-21 | D04942P | | 2 | | D04602J | | 7 | | 050-099 |
| 001 | 22 | | PA | | 85-2 | 28-42-21 | D04942P | | 2 | | D04602J | | 7 | | 150-199, 275-299 |
| 004 | 22 | | PA | | 16-11 | 32-44-11 | D05210J | | 1 | | D04992P | | 4 | | ALL |
| 005 | 20 | | PA | | 75-3 | 28-22-31 | D04942P | | 5 | | D04602J | | 15 | | 050-099 |
| 005 | 20 | | PA | | 85-2 | 28-22-31 | D04942P | | 5 | | D04602J | | 15 | | 150-199, 275-299 |
| 006 | 20 | | PA | | 75-3 | 28-22-31 | D04942P | | 6 | | D04602J | | 16 | | 050-099 |
| 006 | 20 | | PA | | 85-2 | 28-22-31 | D04942P | | 6 | | D04602J | | 16 | | 150-199, 275-299 |
| 007 | 22 | | PA | | 88-5 | 32-44-11 | D04992P | | 7 | | D06012J | | 4 | | 050-099 |
| 007 | 22 | | PA | | 97-10 | 32-44-11 | D04992P | | 7 | | D06012J | | 4 | | 150-199, 275-299 |
| 008 | 18 | | PA | | 88-5 | 32-44-11 | D04992P | | 8 | DL | D06012J | | 2 | | 050-099 |
| 008 | 18 | | PA | | 97-10 | 32-44-11 | D04992P | | 8 | DL | D06012J | | 2 | | 150-199, 275-299 |
| 009 | 18 | | PA | | 4-6 | 32-44-11 | GD02620 | | D.. 2 | | D06012J | | 1 | | 050-099 |
| 009 | 18 | | PA | | 4-0 | 32-44-11 | GD02620 | | D.. 2 | | D06012J | | 1 | | 150-199, 275-299 |
| 010 | 18 | | PA | | 88-5 | 32-44-11 | D04992P | | 10 | DL | D06012J | | 3 | | 050-099 |
| 010 | 18 | | PA | | 97-10 | 32-44-11 | D04992P | | 10 | DL | D06012J | | 3 | | 150-199, 275-299 |
| 012 | 22 | | PA | | 88-5 | 32-44-11 | D04992P | | 12 | | D06012J | | 10 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 4

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0596 | 286T0596 | | | FUELING CONTROL & DEFUELING VALVES (continued) | | | | | | | | | | | | | |
| 012 | 22 | | PA | 97-10 | 32-44-11 | D04992P | | 12 | | | | | D06012J | 10 | | | 150-199, 275-299 |
| 013 | 20 | | PA | 4-6 | 32-44-11 | GD02620 | | D.. | 2 | | | | D06012J | 9 | | | 050-099 |
| 013 | 20 | | PA | 4-0 | 32-44-11 | GD02620 | | D.. | 2 | | | | D06012J | 9 | | | 150-199, 275-299 |
| 014 | 22 | | PA | 88-5 | 32-44-11 | D04992P | | 14 | | | | | D06012J | 8 | | | 050-099 |
| 014 | 22 | | PA | 97-10 | 32-44-11 | D04992P | | 14 | | | | | D06012J | 8 | | | 150-199, 275-299 |
| 015 | 22 | | PA | 78-11 | 32-41-11 | D04992P | | 9 | | | | | D04988J | 2 | | | 050-099 |
| 015 | 22 | | PA | 88-10 | 32-41-11 | D04992P | | 9 | | | | | D04988J | 2 | | | 150-199, 275-299 |
| 016 | 22 | | PA | 78-11 | 32-41-11 | D04992P | | 1 | | | | | D04988J | 1 | | | 050-099 |
| 016 | 22 | | PA | 88-10 | 32-41-11 | D04992P | | 1 | | | | | D04988J | 1 | | | 150-199, 275-299 |
| 017 | 20 | | PA | 49-1 | 28-26-11 | D04540J | | 50 | | | | | D04992P | 17 | | | 050-099 |
| 017 | 20 | | PA | 59-6 | 28-26-11 | D04540J | | 50 | | | | | D04992P | 17 | | | 150-199, 275-299 |
| 018 | 24 | | PK | 39-0 | 21-58-16 | D04992P | | 46 | | | | | D08036P | 23 | | | 050-099 |
| 018 | 24 | | PK | 38-11 | 21-58-16 | D04992P | | 46 | | | | | D08036P | 23 | | | 150-199, 275-299 |
| 019 | 22 | | PA | 39-0 | 21-58-16 | D04992P | | 47 | | | | | D08036P | 24 | | | 050-099 |
| 019 | 22 | | PA | 38-11 | 21-58-16 | D04992P | | 47 | | | | | D08036P | 24 | | | 150-199, 275-299 |
| 020 | 20 | | PA | 13-7 | 28-26-11 | D04942P | | 37 | | | | | SP01518 | | | S | ALL |
| 021 | 20 | | PA | 13-7 | 28-26-11 | D04942P | | 38 | | | | | SP01536 | | | S | ALL |
| 024 | 22 | | PA | 18-2 | 28-41-12 | D04992P | | 40 | | | | | D05196J | 40 | | | ALL |
| 025 | 24 | | PK | 39-0 | 21-58-15 | D04992P | | 45 | | | | | D08036P | 22 | | | 050-099 |
| 025 | 24 | | PK | 38-11 | 21-58-15 | D04992P | | 45 | | | | | D08036P | 22 | | | 150-199, 275-299 |
| 026 | 24 | | PK | 48-7 | 28-21-11 | D05196J | | 27 | | | | | D04540J | 13 | | | 050-099 |
| 026 | 24 | | PK | 59-0 | 28-21-11 | D05196J | | 27 | | | | | D04540J | 13 | | | 150-199, 275-299 |
| 027 | 24 | | PK | 48-7 | 28-21-11 | D05196J | | 28 | | | | | D04540J | 33 | | | 050-099 |
| 027 | 24 | | PK | 59-0 | 28-21-11 | D05196J | | 28 | | | | | D04540J | 33 | | | 150-199, 275-299 |
| 028 | 24 | | PK | 48-7 | 28-21-11 | D05196J | | 29 | | | | | D04540J | 9 | | | 050-099 |
| 028 | 24 | | PK | 59-0 | 28-21-11 | D05196J | | 29 | | | | | D04540J | 9 | | | 150-199, 275-299 |
| 029 | 24 | | PK | 48-7 | 28-21-11 | D05196J | | 30 | | | | | D04540J | 25 | | | 050-099 |
| 029 | 24 | | PK | 59-0 | 28-21-11 | D05196J | | 30 | | | | | D04540J | 25 | | | 150-199, 275-299 |
| 030 | 22 | | PA | 49-1 | 28-21-11 | D04942P | | 7 | | | | | D04540J | 45 | | | 050-099 |
| 030 | 22 | | PA | 59-7 | 28-21-11 | D04942P | | 7 | | | | | D04540J | 45 | | | 150-199, 275-299 |
| 031 | 18 | | PA | 49-1 | 28-21-11 | D04942P | | 15 | | | | | D04540J | 31 | | DK | 050-099 |
| 031 | 18 | | PA | 59-7 | 28-21-11 | D04942P | | 15 | | | | | D04540J | 31 | | DK | 150-156, 162-166, 275-276 |
| 031 | 18 | | PA | 59-7 | 28-21-11 | D04942P | | 15 | | DL | | | D04540J | 31 | | DK | 157, 167-199, 277-299 |
| 032 | 22 | | PA | 49-1 | 28-21-11 | D04942P | | 8 | | | | | D04540J | 30 | | | 050-099 |
| 032 | 22 | | PA | 59-7 | 28-21-11 | D04942P | | 8 | | | | | D04540J | 30 | | | 150-199, 275-299 |
| 033 | 20 | | PA | 49-1 | 28-21-11 | D04942P | | 10 | | | | | D04540J | 14 | | | 050-099 |
| 033 | 20 | | PA | 59-7 | 28-21-11 | D04942P | | 10 | | | | | D04540J | 14 | | | 150-199, 275-299 |
| 034 | 20 | | PA | 49-1 | 28-21-11 | D04942P | | 11 | | | | | D04540J | 34 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 5

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|-----|---|--|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0596 | 286T0596 | | | FUELING CONTROL & DEFUELING VALVES (continued) | | | | | | | | | | | | | | | |
| 034 | 20 | | PA | | 59-7 | 28-21-11 | D04942P | | | | 11 | | | | D04540J | 34 | | | 150-199, 275-299 |
| 035 | 20 | | PA | | 49-1 | 28-21-11 | D04942P | | | | 12 | | | | D04540J | 12 | | | 050-099 |
| 035 | 20 | | PA | | 59-7 | 28-21-11 | D04942P | | | | 12 | | | | D04540J | 12 | | | 150-199, 275-299 |
| 036 | 22 | | PA | | 18-3 | 28-21-11 | D04942P | | | | 13 | | | | D05842J | 7 | | | ALL |
| 037 | 22 | | PA | | 18-3 | 28-21-11 | D04942P | | | | 14 | | | | D05842J | 8 | | | ALL |
| 038 | 22 | | PA | | 18-3 | 28-21-11 | D04942P | | | | 16 | | | | D05842J | 9 | | | ALL |
| 039 | 22 | | PA | | 18-3 | 28-21-11 | D04942P | | | | 17 | | | | D05842J | 10 | | | ALL |
| 040 | 22 | | PA | | 18-3 | 28-21-11 | D04942P | | | | 18 | | | | D05842J | 11 | | | ALL |
| 041R | 22 | | PH | | 16-0 | 26-11-11 | D07992P | | | | 1 | | | | D04938P | 1 | | | ALL |
| 043 | 22 | | PA | | 78-6 | SPARE | D04938P | | | | 3 | | | | D04540J | CAP | Y | | 050-099 |
| 043 | 22 | | PA | | 92-0 | SPARE | D04938P | | | | 3 | | | | D04540J | CAP | Y | | 150-156, 162-166, 275-276 |
| 044 | 22 | | PA | | 78-6 | SPARE | D04938P | | | | 4 | | | | D04540J | 52 | | | 050-099 |
| 044 | 22 | | PA | | 88-5 | SPARE | D04938P | | | | 4 | | | | D04540J | 52 | | | 150-199, 275-299 |
| 046R | 22 | | PH | | 82-6 | 26-11-11 | D07992P | | | | 6 | | | | D04542J | 6 | | | 050-099 |
| 046R | 22 | | PH | | 92-4 | 26-11-11 | D07992P | | | | 6 | | | | D04542J | 6 | | | 150-199, 275-299 |
| 047R | 22 | | PH | | 82-6 | 26-11-11 | D07992P | | | | 7 | | | | D04542J | 2 | | | 050-099 |
| 047R | 22 | | PH | | 92-4 | 26-11-11 | D07992P | | | | 7 | | | | D04542J | 2 | | | 150-199, 275-299 |
| 048R | 22 | | PH | | 82-6 | 26-11-11 | D07992P | | | | 8 | | | | D04542J | 4 | | | 050-099 |
| 048R | 22 | | PH | | 92-4 | 26-11-11 | D07992P | | | | 8 | | | | D04542J | 4 | | | 150-199, 275-299 |
| 049R | 20 | | PH | | 2-7 | 26-11-11 | D07992P | | | | 9 | | | | GD04462 | D.. | 2 | | ALL |
| 050 | 22 | | PA | | 59-6 | SPARE | D04540J | | | | 59 | | | | D04992P | 37 | | | 150-199 |
| 051R | 22 | | PH | | 16-0 | 26-11-12 | D07992P | | | | 11 | | | | D04938P | 6 | | | ALL |
| 056R | 22 | | PH | | 82-6 | 26-11-12 | D07992P | | | | 16 | | | | D04542J | 1 | | | 050-099 |
| 056R | 22 | | PH | | 92-4 | 26-11-12 | D07992P | | | | 16 | | | | D04542J | 1 | | | 150-199, 275-299 |
| 057R | 22 | | PH | | 82-6 | 26-11-12 | D07992P | | | | 17 | | | | D04542J | 5 | | | 050-099 |
| 057R | 22 | | PH | | 92-4 | 26-11-12 | D07992P | | | | 17 | | | | D04542J | 5 | | | 150-199, 275-299 |
| 058R | 22 | | PH | | 82-6 | 26-11-12 | D07992P | | | | 18 | | | | D04542J | 3 | | | 050-099 |
| 058R | 22 | | PH | | 92-4 | 26-11-12 | D07992P | | | | 18 | | | | D04542J | 3 | | | 150-199, 275-299 |
| 059R | 20 | | PH | | 2-7 | 26-11-12 | D07992P | | | | 19 | | | | GD04462 | D.. | 2 | | ALL |
| 060 | 22 | | PA | | 18-3 | 28-21-11 | D04942P | | | | 19 | | | | D05842J | 12 | | | ALL |
| 061 | 24 | | PK | | 12-10 | 31-51-21 | D07992P | | | | 2 | | | | SP00499 | | S | | 050-099 |
| 061 | 24 | | PK | | 50-8 | 31-51-21 | D07992P | | | | 2 | | | | D05842J | 5 | | | 150-154, 275 |
| 061 | 24 | | PK | | 12-8 | 31-51-21 | D07992P | | | | 2 | | | | SP00499 | | S | | 155-199, 276-299 |
| 062 | 24 | | PK | | 12-10 | 31-51-21 | D07992P | | | | 3 | | | | SP00501 | | S | | 050-099 |
| 062 | 24 | | PK | | 50-8 | 31-51-21 | D07992P | | | | 3 | | | | D05842J | 6 | | | 150-154, 275 |
| 062 | 24 | | PK | | 12-8 | 31-51-21 | D07992P | | | | 3 | | | | SP00501 | | S | | 155-199, 276-299 |
| 063 | 24 | | PK | | 18-1 | 73-21-18 | D04938P | | | | 16 | | | | D08036P | 16 | | | 050-099 |
| 063 | 24 | | PK | | 18-0 | 73-21-18 | D04938P | | | | 16 | | | | D08036P | 16 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11
Section W0590
Page 6
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0596 | 286T0596 | | | FUELING CONTROL & DEFUELING VALVES (continued) | | | | | | | | | | | | | |
| 064 | 24 | | PK | 18-1 | 73-21-18 | D04938P | | 17 | | | | | D08036P | 17 | | | 050-099 |
| 064 | 24 | | PK | 18-0 | 73-21-18 | D04938P | | 17 | | | | | D08036P | 17 | | | 150-199, 275-299 |
| 065 | 22 | | PA | 84-2 | 28-21-12 | D08036P | | 4 | | | | | D04540J | 29 | | | 050-099 |
| 065 | 22 | | PA | 94-0 | 28-21-12 | D08036P | | 4 | | | | | D04540J | 29 | | | 150-199, 275-299 |
| 066 | 22 | | PA | 39-0 | 28-21-12 | D08036P | | 5 | | | | | D04992P | 3 | | | 050-099 |
| 066 | 22 | | PA | 38-11 | 28-21-12 | D08036P | | 5 | | | | | D04992P | 3 | | | 150-199, 275-299 |
| 067 | 22 | | PA | 39-0 | 28-21-12 | D08036P | | 6 | | | | | D04992P | 2 | | | 050-099 |
| 067 | 22 | | PA | 38-11 | 28-21-12 | D08036P | | 6 | | | | | D04992P | 2 | | | 150-199, 275-299 |
| 068 | 22 | | PA | 49-1 | 28-21-12 | D04992P | | 5 | | | | | D04540J | 28 | | | 050-099 |
| 068 | 22 | | PA | 59-6 | 28-21-12 | D04992P | | 5 | | | | | D04540J | 28 | | | 150-199, 275-299 |
| 069 | 20 | | PA | 64-2 | 28-21-13 | D04942P | | 27 | | | | | SP01540 | | S | | 050-099 |
| 069 | 20 | | PA | 72-3 | 28-21-13 | D04942P | | 27 | | | | | SP01540 | | S | | 150-199, 275-299 |
| 070 | 20 | | PA | 64-2 | 28-21-13 | D04942P | | 28 | | | | | SP01524 | | S | | 050-099 |
| 070 | 20 | | PA | 72-3 | 28-21-13 | D04942P | | 28 | | | | | SP01524 | | S | | 150-199, 275-299 |
| 071 | 20 | | PA | 64-2 | 28-21-13 | D04942P | | 29 | | | | | SP01542 | | S | | 050-099 |
| 071 | 20 | | PA | 72-3 | 28-21-13 | D04942P | | 29 | | | | | SP01542 | | S | | 150-199, 275-299 |
| 072 | 20 | | PA | 75-10 | 28-21-13 | D04942P | | 30 | | | | | SP01546 | | S | | 050-099 |
| 072 | 20 | | PA | 85-10 | 28-21-13 | D04942P | | 30 | | | | | SP01546 | | S | | 150-199, 275-299 |
| 073 | 20 | | PA | 75-3 | 28-21-13 | D04942P | | 31 | | | | | D04602J | 1 | | | 050-099 |
| 073 | 20 | | PA | 85-2 | 28-21-13 | D04942P | | 31 | | | | | D04602J | 1 | | | 150-199, 275-299 |
| 074 | 20 | | PA | 64-2 | 28-21-13 | D04942P | | 32 | | | | | SP01530 | | S | | 050-099 |
| 074 | 20 | | PA | 72-3 | 28-21-13 | D04942P | | 32 | | | | | SP01530 | | S | | 150-199, 275-299 |
| 075 | 22 | | PA | 21-8 | 28-21-13 | D04540J | | 16 | | | | | SP01526 | | S | | 050-099 |
| 075 | 22 | | PA | 19-10 | 28-21-13 | D04540J | | 16 | | | | | SP01526 | | S | | 150-199, 275-299 |
| 076 | 22 | | PA | 21-8 | 28-21-13 | D04540J | | 15 | | | | | SP01544 | | S | | 050-099 |
| 076 | 22 | | PA | 19-10 | 28-21-13 | D04540J | | 15 | | | | | SP01544 | | S | | 150-199, 275-299 |
| 077 | 22 | | PA | 21-8 | 28-21-13 | D04540J | | 36 | | | | | SP01528 | | S | | 050-099 |
| 077 | 22 | | PA | 19-10 | 28-21-13 | D04540J | | 36 | | | | | SP01528 | | S | | 150-199, 275-299 |
| 078 | 22 | | PA | 31-2 | 28-21-13 | D04540J | | 35 | | | | | SP01548 | | S | | ALL |
| 079 | 22 | | PA | 30-6 | 28-21-13 | D04540J | | 11 | | | | | D04602J | 2 | | | ALL |
| 080 | 22 | | PA | 21-8 | 28-21-13 | D04540J | | 10 | | | | | SP01532 | | S | | 050-099 |
| 080 | 22 | | PA | 19-10 | 28-21-13 | D04540J | | 10 | | | | | SP01532 | | S | | 150-199, 275-299 |
| 081 | 20 | | PA | 127-6 | 29-11-32 | D08036P | | 7 | | | | | SM00006 | | S | | 050-099 |
| 081 | 20 | | PA | 137-4 | 29-11-32 | D08036P | | 7 | | | | | SM00006 | | S | | 150-199, 275-299 |
| 082 | 18 | | HL | 6-7 | 29-11-32 | GD00132 | | D.. | 2 | | | | D00488 | 3 | | | ALL |
| 083 | 18 | | HL | 6-7 | 29-11-32 | GD00132 | | S.. | 2 | | | | D00488 | 1 | | | ALL |
| 084 | 18 | | HL | 6-7 | 29-11-32 | GD00132 | | D.. | 2 | | | | D00488 | 4 | | | ALL |
| 085 | 20 | | PA | 92-11 | 29-11-32 | D04992P | | 16 | | | | | SM00008 | | S | | 050-099 |
| 085 | 20 | | PA | 102-10 | 29-11-32 | D04992P | | 16 | | | | | SM00008 | | S | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 7

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0596 | 286T0596 | | | FUELING CONTROL & DEFUELING VALVES (continued) | | | | | | | | | | | | | |
| 086 | 20 | | PA | 92-11 | 29-11-32 | D04992P | | 15 | | | | | SM00007 | | | S | 050-099 |
| 086 | 20 | | PA | 102-10 | 29-11-32 | D04992P | | 15 | | | | | SM00007 | | | S | 150-199, 275-299 |
| 087 | 18 | | PA | 49-1 | 28-41-12 | D04942P | | 22 | | | | | D04540J | 32 | | DK | 050-099 |
| 087 | 18 | | PA | 59-7 | 28-41-12 | D04942P | | 22 | | | | | D04540J | 32 | | DK | 150-156, 162-166, 275-276 |
| 087 | 18 | | PA | 59-7 | 28-41-12 | D04942P | | 22 | DL | | | | D04540J | 32 | | DK | 157, 167-199, 277-299 |
| 088 | 20 | | PA | 127-6 | 29-11-32 | D08036P | | 1 | | | | | SM00001 | | | S | 050-099 |
| 088 | 20 | | PA | 137-4 | 29-11-32 | D08036P | | 1 | | | | | SM00001 | | | S | 150-199, 275-299 |
| 089 | 12 | | PA | 50-4 | 34-21-31 | D04938P | | 15 | | | | | D04773J | 1 | | | ALL |
| 090 | 18 | | PA | 75-3 | 28-22-21 | D04942P | | 3 | DL | | | | D04602J | 13 | | | 050-099 |
| 090 | 18 | | PA | 85-2 | 28-22-21 | D04942P | | 3 | DL | | | | D04602J | 13 | | | 150-199, 275-299 |
| 091 | 24 | | PK | 48-7 | 28-41-11 | D05196J | | 21 | | | | | D04540J | 57 | | | 050-099 |
| 091 | 24 | | PK | 59-0 | 28-41-11 | D05196J | | 21 | | | | | D04540J | 57 | | | 150-199, 275-299 |
| 092 | 24 | | PK | 48-7 | 28-41-11 | D05196J | | 23 | | | | | D04540J | 58 | | | 050-099 |
| 092 | 24 | | PK | 59-0 | 28-41-11 | D05196J | | 23 | | | | | D04540J | 58 | | | 150-199, 275-299 |
| 093 | 18 | | PA | 75-3 | 28-22-21 | D04942P | | 23 | DL | | | | D04602J | 14 | | | 050-099 |
| 093 | 18 | | PA | 85-2 | 28-22-21 | D04942P | | 23 | DL | | | | D04602J | 14 | | | 150-199, 275-299 |
| 094 | 20 | | PA | 127-6 | 29-11-32 | D08036P | | 3 | | | | | SM00002 | | | S | 050-099 |
| 094 | 20 | | PA | 137-4 | 29-11-32 | D08036P | | 3 | | | | | SM00002 | | | S | 150-199, 275-299 |
| 095 | 18 | | PA | 39-0 | 29-11-32 | D08036P | | 8 | DL | | | | D04992P | 13 | | DL | 050-099 |
| 095 | 18 | | PA | 38-11 | 29-11-32 | D08036P | | 8 | DL | | | | D04992P | 13 | | DL | 150-199, 275-299 |
| 096 | 24 | | PK | 39-0 | 29-11-32 | D08036P | | 11 | | | | | D04992P | 21 | | | 050-099 |
| 096 | 24 | | PK | 38-11 | 29-11-32 | D08036P | | 11 | | | | | D04992P | 21 | | | 150-199, 275-299 |
| 097 | 22 | | PA | 18-1 | 29-11-32 | D08036P | | 12 | | | | | D04938P | 14 | | | 050-099 |
| 097 | 22 | | PA | 18-0 | 29-11-32 | D08036P | | 12 | | | | | D04938P | 14 | | | 150-199, 275-299 |
| 098 | 20 | | PA | 92-11 | 29-11-32 | SM00009 | | | | | | S | D04992P | 6 | | | 050-099 |
| 098 | 20 | | PA | 102-10 | 29-11-32 | SM00009 | | | | | | S | D04992P | 6 | | | 150-199, 275-299 |
| 099 | 18 | | HL | 7-8 | 29-11-32 | D00352 | | 2 | | | | | GD00132 | S.. | 2 | | ALL |
| 100 | 18 | | HL | 7-8 | 29-11-32 | D00352 | | 3 | | | | | GD00132 | D.. | 2 | | ALL |
| 102 | 24 | | PK | 18-2 | 29-11-32 | D05196J | | 36 | | | | | D04992P | 23 | | | ALL |
| 103 | 24 | | PK | 39-1 | 29-21-31 | D04942P | | 26 | | | | | D08036P | 18 | | | 050-099 |
| 103 | 24 | | PK | 39-0 | 29-21-31 | D04942P | | 26 | | | | | D08036P | 18 | | | 150-199, 275-299 |
| 104 | 24 | | PK | 39-1 | 29-21-31 | D04942P | | 36 | | | | | D08036P | 19 | | | 050-099 |
| 104 | 24 | | PK | 39-0 | 29-21-31 | D04942P | | 36 | | | | | D08036P | 19 | | | 150-199, 275-299 |
| 107 | 20 | | PQ | AA | 74-7 | 28-41-23 | D04320J | | 1 | | | | D06078J | 1 | | | 050-099 |
| 107 | 20 | | PQ | AA | 84-6 | 28-41-23 | D04320J | | 1 | | | | D06078J | 1 | | | 150-199, 275-299 |
| 107Z | | | | AA | 0-0 | 28-41-23 | D04320J | | = C1 | | | | D06078J | = C1 | | | ALL |
| 108 | 24 | | PK | | 74-8 | 28-41-23 | D05196J | | 41 | | | | D05884J | 2 | | | 050-099 |
| 108 | 24 | | PK | | 84-7 | 28-41-23 | D05196J | | 41 | | | | D05884J | 2 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 8

Feb 06/2009



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0596 | 286T0596 | | | FUELING CONTROL & DEFUELING VALVES (continued) | | | | | | | | | | | | |
| 109 | 24 | | PK | 74-8 | 28-41-23 | D05196J | | 37 | | | D05884J | | 3 | | 050-099 | |
| 109 | 24 | | PK | 84-7 | 28-41-23 | D05196J | | 37 | | | D05884J | | 3 | | 150-199, 275-299 | |
| 110 | 24 | | PK | 74-8 | 28-41-23 | D05196J | | 38 | | | D05884J | | 4 | | 050-099 | |
| 110 | 24 | | PK | 84-7 | 28-41-23 | D05196J | | 38 | | | D05884J | | 4 | | 150-199, 275-299 | |
| 111 | 24 | | PK | 74-8 | 28-41-23 | D05196J | | 39 | | | D05884J | | 5 | | 050-099 | |
| 111 | 24 | | PK | 84-7 | 28-41-23 | D05196J | | 39 | | | D05884J | | 5 | | 150-199, 275-299 | |
| 112 | 24 | | PK | 74-8 | 28-41-23 | D05884J | | 6 | | | D05196J | | 42 | | 050-099 | |
| 112 | 24 | | PK | 84-7 | 28-41-23 | D05196J | | 42 | | | D05884J | | 6 | | 150-199, 275-299 | |
| 113 | 20 | | PA | 49-1 | 28-26-11 | D04992P | | 26 | | | D04540J | | 17 | | 050-099 | |
| 113 | 20 | | PA | 59-6 | 28-26-11 | D04992P | | 26 | | | D04540J | | 17 | | 150-199, 275-299 | |
| 114 | 20 | | PA | 49-1 | 28-26-11 | D04992P | | 27 | | | D04540J | | 18 | | 050-099 | |
| 114 | 20 | | PA | 59-6 | 28-26-11 | D04992P | | 27 | | | D04540J | | 18 | | 150-199, 275-299 | |
| 117 | 20 | | PA | 49-1 | 28-26-11 | D04992P | | 30 | | | D04540J | | 7 | | 050-099 | |
| 117 | 20 | | PA | 59-6 | 28-26-11 | D04992P | | 30 | | | D04540J | | 7 | | 150-199, 275-299 | |
| 118 | 20 | | PA | 49-1 | 28-26-11 | D04992P | | 31 | | | D04540J | | 8 | | 050-099 | |
| 118 | 20 | | PA | 59-6 | 28-26-11 | D04992P | | 31 | | | D04540J | | 8 | | 150-199, 275-299 | |
| 119 | 20 | | PA | 78-11 | SPARE | D04542J | | 10 | | | D04938P | | 11 | | 050-099 | |
| 119 | 20 | | PA | 88-10 | SPARE | D04542J | | 10 | | | D04938P | | 11 | | 150-199, 275-299 | |
| 120 | 20 | | PA | 78-11 | SPARE | D04542J | | 14 | | | D04938P | | 12 | | 050-099 | |
| 120 | 20 | | PA | 88-10 | SPARE | D04542J | | 14 | | | D04938P | | 12 | | 150-199, 275-299 | |
| 121 | 24 | | PK | 13-7 | 28-26-11 | D04942P | | 34 | | | SP01550 | | | S | ALL | |
| 124 | 22 | | PA | 75-3 | 28-22-21 | D04602J | | 5 | | | D04942P | | 25 | | 050-099 | |
| 124 | 22 | | PA | 85-2 | 28-22-21 | D04602J | | 5 | | | D04942P | | 25 | | 150-199, 275-299 | |
| 125 | 22 | | PA | 75-3 | 28-22-31 | D04942P | | 33 | | | D04602J | | 3 | | 050-099 | |
| 125 | 22 | | PA | 85-2 | 28-22-31 | D04942P | | 33 | | | D04602J | | 3 | | 150-199, 275-299 | |
| 126 | 22 | | PA | 79-0 | 29-11-32 | D04942P | | 4 | | | D04988J | | 7 | | 050-099 | |
| 126 | 22 | | PA | 88-11 | 29-11-32 | D04942P | | 4 | | | D04988J | | 7 | | 150-199, 275-299 | |
| 127 | 20 | | PA | 4-10 | 29-11-32 | GD00432 | | D.. | 2 | | D04988J | | 8 | | ALL | |
| 128 | 20 | | PA | 4-10 | 29-11-32 | GD00432 | | D.. | 2 | | D04988J | | 10 | | ALL | |
| 129 | 22 | | PA | 79-0 | 29-11-32 | D04942P | | 1 | | | D04988J | | 9 | | 050-099 | |
| 129 | 22 | | PA | 88-11 | 29-11-32 | D04942P | | 1 | | | D04988J | | 9 | | 150-199, 275-299 | |
| 130 | 22 | | PA | 79-0 | 29-11-32 | D04942P | | 9 | | | D04988J | | 11 | | 050-099 | |
| 130 | 22 | | PA | 88-11 | 29-11-32 | D04942P | | 9 | | | D04988J | | 11 | | 150-199, 275-299 | |
| 131 | 22 | | PA | 107-11 | 29-32-11 | D04938P | | 13 | | | D04988J | | 3 | | 050-099 | |
| 131 | 22 | | PA | 117-10 | 29-32-11 | D04938P | | 13 | | | D04988J | | 3 | | 150-199, 275-278 | |
| 131 | 22 | | PA | 119-0 | 29-32-11 | D04938P | | 13 | | | D04988J | | 3 | | 280-299 | |
| 132 | 20 | | PA | 4-10 | 29-32-11 | GD00432 | | D.. | 2 | | D04988J | | 4 | | ALL | |
| 135 | 16 | | HL | 55-5 | 25-65-11 | SP02568 | | | | S | D01130 | | A | FM | 050-099 | |
| 135 | 16 | | HL | 55-9 | 25-65-11 | SP02568 | | | | S | D01130 | | A | FM | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 9

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0596 | 286T0596 | | | FUELING CONTROL & DEFUELING VALVES (continued) | | | | | | | | | | | |
| 136 | 16 | | HL | 8-3 | 25-65-11 | GD00132 | D.. | 2 | | D01130 | B | FM | | 050-099 | |
| 136 | 16 | | HL | 8-7 | 25-65-11 | GD00132 | D.. | 2 | | D01130 | B | FM | | 150-199, 275-299 | |
| 143 | 22 | | PA | 16-11 | 32-41-11 | D05210J | | 2 | | D04992P | 18 | | | ALL | |
| 144 | 24 | | PK | 49-1 | 28-41-11 | D04540J | | 19 | | D04992P | 20 | | | 050-099 | |
| 144 | 24 | | PK | 59-6 | 28-41-11 | D04540J | | 19 | | D04992P | 20 | | | 150-199, 275-299 | |
| 145 | 24 | | PK | 49-1 | 28-41-11 | D04540J | | 1 | | D04942P | 24 | | | 050-099 | |
| 145 | 24 | | PK | 59-7 | 28-41-11 | D04540J | | 1 | | D04942P | 24 | | | 150-199, 275-299 | |
| 146 | 20 | | PA | 4-10 | 29-32-11 | D04988J | | 12 | | GD00432 | S.. | 2 | | ALL | |
| 154 | 24 | | PK | 16-11 | 32-42-11 | D04992P | | 51 | | D05210J | 9 | | | ALL | |
| 155 | 24 | | PK | 16-11 | 32-42-11 | D04992P | | 52 | | D05210J | 10 | | | ALL | |
| 156 | 24 | | PK | 16-11 | 32-42-11 | D04992P | | 53 | | D05210J | 11 | | | ALL | |
| 157 | 24 | | PK | 16-11 | 32-42-11 | D04992P | | 54 | | D05210J | 12 | | | ALL | |
| 178 | 18 | | HL | 4-8 | 29-11-32 | SM00001 | | | S | D00488 | 12 | | | ALL | |
| 179 | 18 | | HL | 4-8 | 29-11-32 | SM00002 | | | S | D00488 | 13 | | | ALL | |
| 180 | 18 | | HL | 4-8 | 29-11-32 | SM00006 | | | S | D00488 | 6 | | | ALL | |
| 181 | 18 | | HL | 4-8 | 29-11-32 | SM00007 | | | S | D00488 | 7 | | | ALL | |
| 182 | 18 | | HL | 4-8 | 29-11-32 | SM00008 | | | S | D00488 | 5 | | | ALL | |
| 183 | 18 | | HL | 6-3 | 29-11-32 | SM00009 | | | S | D00352 | 1 | | | ALL | |
| 188 | 24 | | PK | 18-1 | 80-11-21 | D04938P | | 18 | | D08036P | 20 | | | 050-099 | |
| 188 | 24 | | PK | 18-0 | 80-11-21 | D04938P | | 18 | | D08036P | 20 | | | 150-199, 275-299 | |
| 189 | 24 | | PK | 18-1 | 80-11-21 | D04938P | | 22 | | D08036P | 21 | | | 050-099 | |
| 189 | 24 | | PK | 18-0 | 80-11-21 | D04938P | | 22 | | D08036P | 21 | | | 150-199, 275-299 | |
| 199 | 20 | | PA | 8-8 | 28-22-31 | GD00432 | D.. | 2 | | D04602J | 4 | | | 050-099, 155-199, 277-299 | |
| 199 | 20 | | PA | 10-0 | 28-22-31 | GD00432 | D.. | 2 | | D04602J | 4 | | | 150-154, 275-276 | |
| 202B | 24 | | PL | B | 48-7 | 28-41-11 | D05196J | 4 | | D04540J | 21 | | | 050-099 | |
| 202B | 24 | | PL | B | 59-0 | 28-41-11 | D05196J | 4 | | D04540J | 21 | | | 150-199, 275-299 | |
| 202R | 24 | | PL | B | 0-0 | 28-41-11 | D05196J | 5 | | D04540J | 22 | | | ALL | |
| 205B | 24 | | PL | E | 48-7 | 28-41-11 | D05196J | 10 | | D04540J | 41 | | | 050-099 | |
| 205B | 24 | | PL | E | 59-0 | 28-41-11 | D05196J | 10 | | D04540J | 41 | | | 150-199, 275-299 | |
| 205R | 24 | | PL | E | 0-0 | 28-41-11 | D05196J | 11 | | D04540J | 42 | | | ALL | |
| 208B | 24 | | PL | H | 48-7 | 28-41-11 | D05196J | 17 | | D04540J | 3 | | | 050-099 | |
| 208B | 24 | | PL | H | 59-0 | 28-41-11 | D05196J | 17 | | D04540J | 3 | | | 150-199, 275-299 | |
| 208R | 24 | | PL | H | 0-0 | 28-41-11 | D05196J | 18 | | D04540J | 4 | | | ALL | |
| 210B | 24 | | PW | P | 22-1 | 23-41-11 | D04542J | 7 | | SP00163 | | S | | 050-099 | |
| 210B | 24 | | PW | P | 20-2 | 23-41-11 | D04542J | 7 | | SP00163 | | S | | 150-199, 275-299 | |
| 210R | 24 | | PW | P | 0-0 | 23-41-11 | D04542J | 8 | | SP00161 | | S | | ALL | |
| 210Z | | | | P | 0-0 | 23-41-11 | D04542J | 9 | | SP00165 | | S | | ALL | |
| 211B | 24 | | PL | IK | 18-2 | 28-41-11 | D05196J | 14 | | D04942P | 20 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 10

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0596 | 286T0596 | | | FUELING CONTROL & DEFUELING VALVES (continued) | | | | | | | | | | | | |
| 211R | 24 | PL | IK | | 0-0 | 28-41-11 | D05196J | | 15 | | | | D04942P | 21 | | ALL |
| 212B | 24 | PL | IL | | 18-2 | 28-41-11 | D05196J | | 2 | | | | D04992P | 11 | | ALL |
| 212R | 24 | PL | IL | | 0-0 | 28-41-11 | D05196J | | 8 | | | | D04992P | 19 | | ALL |
| 213B | 24 | PW | IM | | 127-6 | 29-11-32 | D08036P | | 10 | | | | SM00003 | | S | 050-099 |
| 213B | 24 | PW | IM | | 137-4 | 29-11-32 | D08036P | | 10 | | | | SM00003 | | S | 150-199, 275-299 |
| 213R | 24 | PW | IM | | 0-0 | 29-11-32 | D08036P | | 9 | | | | SM00004 | | S | ALL |
| 213Z | | | IM | | 0-0 | 29-11-32 | D08036P | | 2 | | | | SM00005 | | S | ALL |
| 215B | 20 | HQ | IP | | 4-8 | 29-11-32 | SM00003 | | | S | | | D00488 | 10 | | ALL |
| 215R | 20 | HQ | IP | | 0-0 | 29-11-32 | SM00004 | | | S | | | D00488 | 9 | | ALL |
| 215Z | | | IP | | 0-0 | 29-11-32 | SM00005 | | | S | | | D00488 | 2 | | ALL |
| 216B | 24 | PL | IQ | | 18-2 | 28-41-11 | D05196J | | 24 | | | | D04992P | 24 | | ALL |
| 216R | 24 | PL | IQ | | 0-0 | 28-41-11 | D05196J | | 25 | | | | D04992P | 25 | | ALL |
| 217B | 24 | PL | IR | | 48-7 | SPARE | D05842J | | 14 | | | | D04540J | 26 | | 050-099 |
| 217B | 24 | PL | IR | | 59-0 | SPARE | D05842J | | 14 | | | | D04540J | 26 | | 150-199 |
| 217R | 24 | PL | IR | | 0-0 | SPARE | D05842J | | 13 | | | | D04540J | 27 | | 050-099, 150-199 |
| 218B | 22 | PB | AB | | 59-6 | SPARE | D04540J | | 54 | | | | D04992P | 34 | | 150-199 |
| 218R | 22 | PB | AB | | 0-0 | SPARE | D04540J | | 53 | | | | D04992P | 33 | | 150-199 |
| 219B | 22 | PB | AC | | 59-6 | SPARE | D04540J | | 56 | | | | D04992P | 36 | | 150-199 |
| 219R | 22 | PB | AC | | 0-0 | SPARE | D04540J | | 55 | | | | D04992P | 35 | | 150-199 |
| 220B | 24 | PL | AD | | 59-5 | SPARE | D04542J | | | CAP | Y | | D05842J | 17 | | 150-199 |
| 220R | 24 | PL | AD | | 0-0 | SPARE | D04542J | | | CAP | Y | | D05842J | 16 | | 150-199 |
| 221B | 24 | PL | AE | | 59-5 | SPARE | D04542J | | | CAP | Y | | D05842J | 22 | | 150-199 |
| 221R | 24 | PL | AE | | 0-0 | SPARE | D04542J | | | CAP | Y | | D05842J | 21 | | 150-199 |
| 301B | 24 | PM | MA | | 48-7 | 28-41-11 | D05196J | | 12 | | | | D04540J | 43 | | 050-099 |
| 301B | 24 | PM | MA | | 59-0 | 28-41-11 | D05196J | | 12 | | | | D04540J | 43 | | 150-199, 275-299 |
| 301R | 24 | PM | MA | | 0-0 | 28-41-11 | D05196J | | 13 | | | | D04540J | 44 | | ALL |
| 301Y | 24 | PM | MA | | 0-0 | 28-41-11 | D05196J | | 9 | | | | D04540J | 40 | | ALL |
| 302B | 24 | PM | MB | | 48-7 | 28-41-11 | D05196J | | 6 | | | | D04540J | 23 | | 050-099 |
| 302B | 24 | PM | MB | | 59-0 | 28-41-11 | D05196J | | 6 | | | | D04540J | 23 | | 150-199, 275-299 |
| 302R | 24 | PM | MB | | 0-0 | 28-41-11 | D05196J | | 7 | | | | D04540J | 24 | | ALL |
| 302Y | 24 | PM | MB | | 0-0 | 28-41-11 | D05196J | | 3 | | | | D04540J | 20 | | ALL |
| 303B | 24 | PM | MC | | 48-7 | 28-41-11 | D05196J | | 19 | | | | D04540J | 5 | | 050-099 |
| 303B | 24 | PM | MC | | 59-0 | 28-41-11 | D05196J | | 19 | | | | D04540J | 5 | | 150-199, 275-299 |
| 303R | 24 | PM | MC | | 0-0 | 28-41-11 | D05196J | | 20 | | | | D04540J | 6 | | ALL |
| 303Y | 24 | PM | MC | | 0-0 | 28-41-11 | D05196J | | 16 | | | | D04540J | 2 | | ALL |
| 305B | 24 | PM | AF | | 59-5 | SPARE | D04542J | | | CAP | Y | | D05842J | 25 | | 150-199 |
| 305R | 24 | PM | AF | | 0-0 | SPARE | D04542J | | | CAP | Y | | D05842J | 24 | | 150-199 |
| 305Y | 24 | PM | AF | | 0-0 | SPARE | D04542J | | | CAP | Y | | D05842J | 26 | | 150-199 |
| 308B | 24 | PM | MH | | 48-7 | SPARE | D05842J | | 2 | | | | D04540J | 60 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 11

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|---|-------|-------------|-------|---------|----------|---------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0596 | 286T0596 | FUELING CONTROL & DEFUELING VALVES (continued) | | | | | | | | | | | | | |
| 308B | 24 | PM | MH | | 59-0 | SPARE | D05842J | | 2 | | D04540J | | 60 | | 150-199 |
| 308R | 24 | PM | MH | | 0-0 | SPARE | D05842J | | 1 | | D04540J | | 39 | | 050-099, 150-199 |
| 308Y | 24 | PM | MH | | 0-0 | SPARE | D05842J | | 3 | | D04540J | | 61 | | 050-099, 150-199 |
| 401B | 24 | PN | M | | 48-7 | | 28-21-11 | D05196J | 31 | | D04540J | | 46 | | 050-099 |
| 401B | 24 | PN | M | | 59-0 | | 28-21-11 | D05196J | 31 | | D04540J | | 46 | | 150-199, 275-299 |
| 401G | 24 | PN | M | | 0-0 | | 28-21-11 | D05196J | 32 | | D04540J | | 47 | | ALL |
| 401R | 24 | PN | M | | 0-0 | | 28-21-11 | D05196J | 33 | | D04540J | | 48 | | ALL |
| 401Y | 24 | PN | M | | 0-0 | | 28-21-11 | D05196J | 34 | | D04540J | | 49 | | ALL |
| 500 | 18 | UA | | | 49-1 | | 28-21-11 | D04942P | 42 | DL | D04540J | | 51 | DK | 050-099 |
| 500 | 18 | UA | | | 65-0 | | 28-21-11 | D04942P | 42 | DL | D04540J | | 51 | DK | 150-156, 162-166, 275-276 |
| 500 | 18 | PA | | | 59-7 | | 28-21-11 | D04942P | 44 | DL | D04540J | | 51 | DK | 157, 167-199, 277-299 |
| 501 | 24 | PK | | | 39-0 | | 28-22-12 | D04992P | 42 | | D08036P | | 13 | | 050-099 |
| 501 | 24 | PK | | | 38-11 | | 28-22-12 | D04992P | 42 | | D08036P | | 13 | | 150-199, 275-299 |
| 502 | 24 | PK | | | 38-11 | SPARE | | D04992P | 43 | | D08036P | | 14 | | 150-154, 275-276 |
| 503 | 24 | PK | | | 38-11 | SPARE | | D04992P | 44 | | D08036P | | 15 | | 150-154, 275-276 |
| 504 | 22 | PA | | | 33-5 | | 32-42-11 | D04942P | 43 | | D04938P | | 28 | | ALL |
| 506 | 22 | PA | | | 33-5 | SPARE | | D04942P | 41 | | D04938P | | 26 | | 050-099 |
| 511 | 18 | PA | | | 49-6 | SPARE | | D04942P | | CAP Y | D04542J | | 11 | | 050-099 |
| 511 | 18 | PA | | | 60-0 | SPARE | | D04942P | | CAP Y | D04542J | | 11 | | 150-156, 162-166, 275-276 |
| 511 | 18 | PA | | | 59-11 | SPARE | | D04942P | 42 | DL | D04542J | | 11 | | 157, 167-199 |
| 512 | 24 | PK | | | 49-0 | SPARE | | D05842J | 4 | | D04542J | | 12 | | 050-099 |
| 512 | 24 | PK | | | 59-5 | SPARE | | D05842J | 4 | | D04542J | | 12 | | 150-199 |
| W0597 | 286T0597 | RO SERVO ACTR C | | | | | | | | | | | | | |
| 006 | 20 | UA | | | 25-2 | | 22-11-32 | D00187 | 2 | | D04523J | | 3 | | ALL |
| 007 | 20 | UA | | | 25-2 | | 22-11-32 | D00187 | 18 | | D04523J | | 9 | | ALL |
| 008 | 18 | UA | | | 1-8 | | 22-11-32 | D00187 | 17 | | GD00185 | | D.. | N | ALL |
| 009 | 18 | UA | | | 1-8 | | 22-11-32 | D00187 | 1 | | GD00185 | | D.. | N | ALL |
| 010 | 18 | UA | | | 1-10 | | 22-11-32 | D00187 | 19 | | GD00187 | | S.. | N | ALL |
| 202B | 20 | UB | IB | | 25-2 | | 22-11-31 | D04523J | 8 | | SM00004 | | 9 | | ALL |
| 202R | 20 | UB | IB | | 0-0 | | 22-11-31 | D04523J | 7 | | SM00003 | | 9 | | ALL |
| 205B | 20 | UB | IE | | 0-6 | | 22-11-31 | D00187 | 7 | | SM00004 | | 9 | | ALL |
| 205R | 20 | UB | IE | | 0-0 | | 22-11-31 | D00187 | 8 | | SM00003 | | 9 | | ALL |
| 206B | 20 | UB | IF | | 0-6 | | 22-11-31 | D00187 | 12 | | SM00004 | | 9 | | ALL |
| 206R | 20 | UB | IF | | 0-0 | | 22-11-31 | D00187 | 13 | | SM00003 | | 9 | | ALL |
| 210B | 20 | UB | IJ | | 25-2 | | 22-13-31 | D04523J | 2 | | SM00008 | | 9 | | ALL |
| 210R | 20 | UB | IJ | | 0-0 | | 22-13-31 | D04523J | 1 | | SM00007 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 12

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0597 | 286T0597 | | | RO SERVO ACTR C (continued) | | | | | | | | | | | | |
| 211B | 20 | UB | IK | 0-6 | 22-13-31 | D00187 | | 6 | | | SM00008 | | 9 | | ALL | |
| 211R | 20 | UB | IK | 0-0 | 22-13-31 | D00187 | | 5 | | | SM00007 | | 9 | | ALL | |
| 212B | 20 | UB | IL | 0-6 | 22-13-31 | D00187 | | 4 | | | SM00008 | | 9 | | ALL | |
| 212R | 20 | UB | IL | 0-0 | 22-13-31 | D00187 | | 3 | | | SM00007 | | 9 | | ALL | |
| 303B | 20 | UC | MC | 25-2 | 22-13-31 | D04523J | | 11 | | | D00187 | 15 | | | ALL | |
| 303R | 20 | UC | MC | 0-0 | 22-13-31 | D04523J | | 10 | | | D00187 | 16 | | | ALL | |
| 303Y | 20 | UC | MC | 0-0 | 22-13-31 | D04523J | | 12 | | | D00187 | 14 | | | ALL | |
| 304B | 20 | UC | MD | 25-2 | 22-13-31 | D04523J | | 14 | | | D00187 | 10 | | | ALL | |
| 304R | 20 | UC | MD | 0-0 | 22-13-31 | D04523J | | 13 | | | D00187 | 11 | | | ALL | |
| 304Y | 20 | UC | MD | 0-0 | 22-13-31 | D04523J | | 15 | | | D00187 | 9 | | | ALL | |
| W0598 | 286T0598 | | | OVER HEAT & FIRE DETECTION & FUEL QUANTITY INDICATION | | | | | | | | | | | | |
| 004 | 18 | PA | | 68-7 | 28-22-21 | D05188P | | 15 | DK | | D05520J | 1 | | | 050-099 | |
| 004 | 18 | PA | | 78-7 | 28-22-21 | D05188P | | 15 | DK | | D05520J | 1 | | | 150-199, 275-299 | |
| 007 | 24 | PK | | 24-11 | 28-41-11 | D04940P | | 11 | | | D04944J | 7 | | | 050-099 | |
| 007 | 24 | PK | | 25-0 | 28-41-11 | D04940P | | 11 | | | D04944J | 7 | | | 150-199, 275-299 | |
| 008 | 24 | PK | | 24-11 | 28-41-11 | D04940P | | 18 | | | D04944J | 14 | | | 050-099 | |
| 008 | 24 | PK | | 25-0 | 28-41-11 | D04940P | | 18 | | | D04944J | 14 | | | 150-199, 275-299 | |
| 009 | 24 | PK | | 24-11 | 28-41-11 | D04940P | | 25 | | | D04944J | 21 | | | 050-099 | |
| 009 | 24 | PK | | 25-0 | 28-41-11 | D04940P | | 25 | | | D04944J | 21 | | | 150-199, 275-299 | |
| 010 | 24 | PK | | 24-11 | 28-41-11 | D04940P | | 32 | | | D04944J | 28 | | | 050-099 | |
| 010 | 24 | PK | | 25-0 | 28-41-11 | D04940P | | 32 | | | D04944J | 28 | | | 150-199, 275-299 | |
| 014 | 12 | PA | | 25-7 | 34-21-21 | D04940P | | 56 | | | D05680J | 2 | | | 050-099 | |
| 014 | 12 | PA | | 25-9 | 34-21-21 | D04940P | | 56 | | | D05680J | 2 | | | 150-199, 275-299 | |
| 015 | 24 | PK | | 24-3 | 31-51-21 | D07996P | | 3 | | | SP00497 | | S | | 050-099 | |
| 015 | 24 | PK | | 23-3 | 31-51-21 | D07996P | | 3 | | | D04944J | 5 | | | 150-154, 275 | |
| 015 | 24 | PK | | 24-2 | 31-51-21 | D07996P | | 3 | | | SP00497 | | S | | 155-199, 276-299 | |
| 020 | 20 | PA | | 66-3 | 28-26-11 | SP01518 | | | S | | D05520J | 6 | | | 050-099 | |
| 020 | 20 | PA | | 76-1 | 28-26-11 | SP01518 | | | S | | D05520J | 6 | | | 150-199, 275-299 | |
| 021 | 20 | PA | | 66-3 | 28-26-11 | SP01536 | | | S | | D05520J | 7 | | | 050-099 | |
| 021 | 20 | PA | | 76-1 | 28-26-11 | SP01536 | | | S | | D05520J | 7 | | | 150-199, 275-299 | |
| 024 | 20 | PA | | 31-1 | 28-21-13 | SP01540 | | | S | | D05520J | 3 | | | 050-099 | |
| 024 | 20 | PA | | 30-11 | 28-21-13 | SP01540 | | | S | | D05520J | 3 | | | 150-199, 275-299 | |
| 025 | 20 | PA | | 31-1 | 28-21-13 | SP01524 | | | S | | D05520J | 5 | | | 050-099 | |
| 025 | 20 | PA | | 30-11 | 28-21-13 | SP01524 | | | S | | D05520J | 5 | | | 150-199, 275-299 | |
| 027 | 22 | PA | | 31-1 | 28-21-13 | SP01526 | | | S | | D05520J | 2 | | | 050-099 | |
| 027 | 22 | PA | | 30-11 | 28-21-13 | SP01526 | | | S | | D05520J | 2 | | | 150-199, 275-299 | |
| 028 | 22 | PA | | 31-1 | 28-21-13 | SP01544 | | | S | | D05520J | 4 | | | 050-099 | |
| 028 | 22 | PA | | 30-11 | 28-21-13 | SP01544 | | | S | | D05520J | 4 | | | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 13

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|----------|-------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0598 | 286T0598 | | | OVER HEAT & FIRE DETECTION & FUEL QUANTITY INDICATION (continued) | | | | | | | | | | | |
| 029 | 20 | PA | | 4-8 | 28-21-13 | | D05520J | 21 | | | GD00854 | D.. | 2 | | ALL |
| 030 | 20 | PA | | 4-8 | 28-21-13 | | D05520J | 20 | | | GD00854 | D.. | 2 | | ALL |
| 041R | 22 | PH | | 25-11 | 26-11-21 | | D07996P | 1 | | | D04940P | | 1 | | 050-099 |
| 041R | 22 | PH | | 25-9 | 26-11-21 | | D07996P | 1 | | | D04940P | | 1 | | 150-199, 275-299 |
| 046R | 22 | PH | | 54-11 | 26-11-21 | | D07996P | 7 | | | D05518J | | 1 | | 050-099 |
| 046R | 22 | PH | | 64-11 | 26-11-21 | | D07996P | 7 | | | D05518J | | 1 | | 150-199, 275-299 |
| 047R | 22 | PH | | 54-11 | 26-11-21 | | D07996P | 6 | | | D05518J | | 2 | | 050-099 |
| 047R | 22 | PH | | 64-11 | 26-11-21 | | D07996P | 6 | | | D05518J | | 2 | | 150-199, 275-299 |
| 048R | 22 | PH | | 54-11 | 26-11-21 | | D07996P | 8 | | | D05518J | | 3 | | 050-099 |
| 048R | 22 | PH | | 64-11 | 26-11-21 | | D07996P | 8 | | | D05518J | | 3 | | 150-199, 275-299 |
| 049R | 20 | PH | | 2-3 | 26-11-21 | | D07996P | 9 | | | GD04462 | D.. | 2 | | 050-099 |
| 049R | 20 | PH | | 2-1 | 26-11-21 | | D07996P | 9 | | | GD04462 | D.. | 2 | | 150-199, 275-299 |
| 051R | 22 | PH | | 25-11 | 26-11-22 | | D07996P | 11 | | | D04940P | | 6 | | 050-099 |
| 051R | 22 | PH | | 25-9 | 26-11-22 | | D07996P | 11 | | | D04940P | | 6 | | 150-199, 275-299 |
| 056R | 22 | PH | | 54-11 | 26-11-22 | | D07996P | 17 | | | D05518J | | 4 | | 050-099 |
| 056R | 22 | PH | | 64-11 | 26-11-22 | | D07996P | 17 | | | D05518J | | 4 | | 150-199, 275-299 |
| 057R | 22 | PH | | 54-11 | 26-11-22 | | D07996P | 18 | | | D05518J | | 5 | | 050-099 |
| 057R | 22 | PH | | 64-11 | 26-11-22 | | D07996P | 18 | | | D05518J | | 5 | | 150-199, 275-299 |
| 058R | 22 | PH | | 54-11 | 26-11-22 | | D07996P | 16 | | | D05518J | | 6 | | 050-099 |
| 058R | 22 | PH | | 64-11 | 26-11-22 | | D07996P | 16 | | | D05518J | | 6 | | 150-199, 275-299 |
| 059R | 20 | PH | | 2-3 | 26-11-22 | | D07996P | 19 | | | GD04462 | D.. | 2 | | 050-099 |
| 059R | 20 | PH | | 2-1 | 26-11-22 | | D07996P | 19 | | | GD04462 | D.. | 2 | | 150-199, 275-299 |
| 060 | 20 | PA | | 68-7 | 27-11-22 | | D05188P | 7 | | | D05520J | | 11 | | 050-099 |
| 060 | 20 | PA | | 78-7 | 27-11-22 | | D05188P | 7 | | | D05520J | | 11 | | 150-199, 275-299 |
| 061 | 20 | PA | | 68-7 | 27-11-22 | | D05188P | 8 | | | D05520J | | 14 | | 050-099 |
| 061 | 20 | PA | | 78-7 | 27-11-22 | | D05188P | 8 | | | D05520J | | 14 | | 150-199, 275-299 |
| 062 | 18 | PA | | 68-7 | 27-11-22 | | D05188P | 9 | DK | | D05520J | | 12 | | 050-099 |
| 062 | 18 | PA | | 78-7 | 27-11-22 | | D05188P | 9 | DK | | D05520J | | 12 | | 150-199, 275-299 |
| 063 | 18 | PA | | 68-7 | 27-11-22 | | D05188P | 10 | DK | | D05520J | | 13 | | 050-099 |
| 063 | 18 | PA | | 78-7 | 27-11-22 | | D05188P | 10 | DK | | D05520J | | 13 | | 150-199, 275-299 |
| 064 | 24 | PK | | 15-6 | 28-22-11 | | D04940P | 42 | | | D05188P | | 11 | | 050-099 |
| 064 | 24 | PK | | 15-5 | 28-22-11 | | D04940P | 42 | | | D05188P | | 11 | | 150-199, 275-299 |
| 065 | 18 | PA | | 68-7 | 28-22-21 | | D05520J | 15 | | | D05188P | | 12 | DK | 050-099 |
| 065 | 18 | PA | | 78-7 | 28-22-21 | | D05520J | 15 | | | D05188P | | 12 | DK | 150-199, 275-299 |
| 066 | 24 | PK | | 24-3 | 31-51-21 | | D07996P | 2 | | | SP00495 | | S | | 050-099 |
| 066 | 24 | PK | | 23-3 | 31-51-21 | | D07996P | 2 | | | D04944J | | 4 | | 150-154, 275 |
| 066 | 24 | PK | | 24-2 | 31-51-21 | | D07996P | 2 | | | SP00495 | | S | | 155-199, 276-299 |
| 070 | 20 | PA | | 66-3 | 28-26-11 | | SP01550 | | S | | D05520J | | 18 | | 050-099 |
| 070 | 20 | PA | | 76-1 | 28-26-11 | | SP01550 | | S | | D05520J | | 18 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 14

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|---|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0598 | 286T0598 | | | OVER HEAT & FIRE DETECTION & FUEL QUANTITY INDICATION (continued) | | | | | | | | | | | | | |
| 071 | 22 | | PA | 68-7 | 28-22-21 | D05520J | | 17 | | | | | D05188P | 14 | | | 050-099 |
| 071 | 22 | | PA | 78-7 | 28-22-21 | D05520J | | 17 | | | | | D05188P | 14 | | | 150-199, 275-299 |
| 072 | 18 | | PA | 4-8 | 27-11-22 | D05520J | | 19 | | | | | GD00852 | D.. | 2 | | ALL |
| 081 | 22 | | PA | 24-11 | SPARE | D04940P | | 46 | | | | | D04944J | 37 | | | 050-099 |
| 081 | 22 | | PA | 25-0 | SPARE | D04940P | | 46 | | | | | D04944J | 37 | | | 150-199, 275-299 |
| 082 | 22 | | PA | 24-11 | SPARE | D04940P | | 47 | | | | | D04944J | 38 | | | 050-099 |
| 082 | 22 | | PA | 25-0 | SPARE | D04940P | | 47 | | | | | D04944J | 38 | | | 150-199, 275-299 |
| 110 | 20 | | W4 | W | 51-6 | 28-21-12 | D08038P | 6 | | | | | D06114J | 3 | | | 050-099 |
| 110 | 20 | | W4 | W | 61-7 | 28-21-12 | D08038P | 6 | | | | | D06114J | 3 | | | 150-199, 275-299 |
| 110Z | | | | W | 0-0 | 28-21-12 | D08038P | 5 | | | | | D06114J | 2 | | | ALL |
| 111 | 20 | | W4 | X | 51-6 | 28-21-12 | D08038P | 8 | | | | | D06114J | 1 | | | 050-099 |
| 111 | 20 | | W4 | X | 61-7 | 28-21-12 | D08038P | 8 | | | | | D06114J | 1 | | | 150-199, 275-299 |
| 111Z | | | | X | 0-0 | 28-21-12 | D08038P | | | FA | | | D06114J | =C1 | | | ALL |
| 112 | 20 | | W4 | Y | 60-11 | 28-21-12 | D08038P | 4 | | | | | D06116J | 3 | | | 050-099 |
| 112 | 20 | | W4 | Y | 71-4 | 28-21-12 | D08038P | 4 | | | | | D06116J | 3 | | | 150-199, 275-299 |
| 112Z | | | | Y | 0-0 | 28-21-12 | D08038P | 1 | | | | | D06116J | 2 | | | ALL |
| 113 | 20 | | W4 | Z | 60-11 | 28-21-12 | D08038P | 11 | | | | | D06116J | 1 | | | 050-099 |
| 113 | 20 | | W4 | Z | 71-4 | 28-21-12 | D08038P | 11 | | | | | D06116J | 1 | | | 150-199, 275-299 |
| 113Z | | | | Z | 0-0 | 28-21-12 | D08038P | | | FB | | | D06116J | =C1 | | | ALL |
| 201B | 24 | | PL | A | 24-11 | 28-41-11 | D04940P | 12 | | | | | D04944J | 8 | | | 050-099 |
| 201B | 24 | | PL | A | 25-0 | 28-41-11 | D04940P | 12 | | | | | D04944J | 8 | | | 150-199, 275-299 |
| 201R | 24 | | PL | A | 0-0 | 28-41-11 | D04940P | 13 | | | | | D04944J | 9 | | | ALL |
| 202B | 24 | | PL | B | 24-11 | 28-41-11 | D04940P | 14 | | | | | D04944J | 10 | | | 050-099 |
| 202B | 24 | | PL | B | 25-0 | 28-41-11 | D04940P | 14 | | | | | D04944J | 10 | | | 150-199, 275-299 |
| 202R | 24 | | PL | B | 0-0 | 28-41-11 | D04940P | 15 | | | | | D04944J | 11 | | | ALL |
| 203B | 24 | | PL | C | 24-11 | 28-41-11 | D04940P | 16 | | | | | D04944J | 12 | | | 050-099 |
| 203B | 24 | | PL | C | 25-0 | 28-41-11 | D04940P | 16 | | | | | D04944J | 12 | | | 150-199, 275-299 |
| 203R | 24 | | PL | C | 0-0 | 28-41-11 | D04940P | 17 | | | | | D04944J | 13 | | | ALL |
| 204B | 24 | | PL | D | 24-11 | 28-41-11 | D04940P | 19 | | | | | D04944J | 15 | | | 050-099 |
| 204B | 24 | | PL | D | 25-0 | 28-41-11 | D04940P | 19 | | | | | D04944J | 15 | | | 150-199, 275-299 |
| 204R | 24 | | PL | D | 0-0 | 28-41-11 | D04940P | 20 | | | | | D04944J | 16 | | | ALL |
| 205B | 24 | | PL | E | 24-11 | 28-41-11 | D04940P | 21 | | | | | D04944J | 17 | | | 050-099 |
| 205B | 24 | | PL | E | 25-0 | 28-41-11 | D04940P | 21 | | | | | D04944J | 17 | | | 150-199, 275-299 |
| 205R | 24 | | PL | E | 0-0 | 28-41-11 | D04940P | 22 | | | | | D04944J | 18 | | | ALL |
| 206B | 24 | | PL | F | 24-11 | 28-41-11 | D04940P | 23 | | | | | D04944J | 19 | | | 050-099 |
| 206B | 24 | | PL | F | 25-0 | 28-41-11 | D04940P | 23 | | | | | D04944J | 19 | | | 150-199, 275-299 |
| 206R | 24 | | PL | F | 0-0 | 28-41-11 | D04940P | 24 | | | | | D04944J | 20 | | | ALL |
| 207B | 24 | | PL | G | 24-11 | 28-41-11 | D04940P | 26 | | | | | D04944J | 22 | | | 050-099 |
| 207B | 24 | | PL | G | 25-0 | 28-41-11 | D04940P | 26 | | | | | D04944J | 22 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 15

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|--|-------|-------------|----------|---------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0598 | 286T0598 | OVER HEAT & FIRE DETECTION & FUEL QUANTITY INDICATION (continued) | | | | | | | | | | | | | |
| 207R | 24 | PL | G | 0-0 | 28-41-11 | D04940P | | 27 | | | D04944J | | 23 | | ALL |
| 208B | 24 | PL | H | 24-11 | 28-41-11 | D04940P | | 28 | | | D04944J | | 24 | | 050-099 |
| 208B | 24 | PL | H | 25-0 | 28-41-11 | D04940P | | 28 | | | D04944J | | 24 | | 150-199, 275-299 |
| 208R | 24 | PL | H | 0-0 | 28-41-11 | D04940P | | 29 | | | D04944J | | 25 | | ALL |
| 209B | 24 | PL | K | 24-11 | 28-41-11 | D04940P | | 30 | | | D04944J | | 26 | | 050-099 |
| 209B | 24 | PL | K | 25-0 | 28-41-11 | D04940P | | 30 | | | D04944J | | 26 | | 150-199, 275-299 |
| 209R | 24 | PL | K | 0-0 | 28-41-11 | D04940P | | 31 | | | D04944J | | 27 | | ALL |
| 210B | 24 | PL | M | 24-11 | 28-41-11 | D04940P | | 33 | | | D04944J | | 29 | | 050-099 |
| 210B | 24 | PL | M | 25-0 | 28-41-11 | D04940P | | 33 | | | D04944J | | 29 | | 150-199, 275-299 |
| 210R | 24 | PL | M | 0-0 | 28-41-11 | D04940P | | 34 | | | D04944J | | 30 | | ALL |
| 211B | 24 | PL | N | 24-11 | 28-41-11 | D04940P | | 35 | | | D04944J | | 31 | | 050-099 |
| 211B | 24 | PL | N | 25-0 | 28-41-11 | D04940P | | 35 | | | D04944J | | 31 | | 150-199, 275-299 |
| 211R | 24 | PL | N | 0-0 | 28-41-11 | D04940P | | 36 | | | D04944J | | 32 | | ALL |
| 212B | 24 | PL | P | 24-11 | 28-41-11 | D04940P | | 37 | | | D04944J | | 33 | | 050-099 |
| 212B | 24 | PL | P | 25-0 | 28-41-11 | D04940P | | 37 | | | D04944J | | 33 | | 150-199, 275-299 |
| 212R | 24 | PL | P | 0-0 | 28-41-11 | D04940P | | 38 | | | D04944J | | 34 | | ALL |
| 213B | 24 | PL | R | 24-11 | 28-41-11 | D04940P | | 39 | | | D04944J | | 35 | | 050-099 |
| 213B | 24 | PL | R | 25-0 | 28-41-11 | D04940P | | 39 | | | D04944J | | 35 | | 150-199, 275-299 |
| 213R | 24 | PL | R | 0-0 | 28-41-11 | D04940P | | 41 | | | D04944J | | 36 | | ALL |
| 218B | 24 | PL | S | 17-9 | 28-41-11 | D04944J | | 3 | | | D05188P | | 3 | | 050-099 |
| 218B | 24 | PL | S | 17-11 | 28-41-11 | D04944J | | 3 | | | D05188P | | 3 | | 150-199, 275-299 |
| 218R | 24 | PL | S | 0-0 | 28-41-11 | D04944J | | 2 | | | D05188P | | 2 | | ALL |
| 801 | 22 | PA | | 24-11 | SPARE | D04940P | | 48 | | | D04944J | | 39 | | 050-099 |
| 801 | 22 | PA | | 25-0 | SPARE | D04940P | | 48 | | | D04944J | | 39 | | 150-199, 275-299 |
| 802 | 22 | PA | | 15-6 | SPARE | D04940P | | 49 | | | D05188P | | 16 | | 050-099 |
| 802 | 22 | PA | | 15-5 | SPARE | D04940P | | 49 | | | D05188P | | 16 | | 150-199, 275-299 |
| 803R | 20 | PH | | 56-7 | SPARE | D04940P | | 43 | | | D05518J | | 7 | | 050-099 |
| 803R | 20 | PH | | 66-8 | SPARE | D04940P | | 43 | | | D05518J | | 7 | | 150-199, 275-299 |
| FRA | | | | 0-0 | 28-21-12 | D08038P | | 2 | | | D08038P | | | FA | ALL |
| FRB | | | | 0-0 | 28-21-12 | D08038P | | 7 | | | D08038P | | | FA | ALL |
| FRC | | | | 0-0 | 28-21-12 | D08038P | | 9 | | | D08038P | | | FA | ALL |
| FRD | | | | 0-0 | 28-21-12 | D08038P | | 3 | | | D08038P | | | FB | ALL |
| FRE | | | | 0-0 | 28-21-12 | D08038P | | 10 | | | D08038P | | | FB | ALL |
| FRF | | | | 0-0 | 28-21-12 | D08038P | | 12 | | | D08038P | | | FB | ALL |
| W0599 | 286T0599 | RO SERVO ACTR R | | | | | | | | | | | | | |
| 006 | 20 | UA | | 25-6 | 22-11-22 | D00195 | | 2 | | | D04527J | | 3 | | ALL |
| 007 | 20 | UA | | 25-6 | 22-11-22 | D00195 | | 18 | | | D04527J | | 9 | | ALL |
| 008 | 18 | UA | | 1-10 | 22-11-22 | D00195 | | 17 | | | GD00165 | | D.. | N | ALL |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 16

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0599 | 286T0599 | | | RO SERVO ACTR R (continued) | | | | | | | | | | | |
| 009 | 18 | | UA | | 1-10 | 22-11-22 | D00195 | | | | GD00165 | D.. | N | | ALL |
| 010 | 18 | | UA | | 1-11 | 22-11-22 | D00195 | 19 | | | GD00167 | S.. | N | | ALL |
| 202B | 20 | | UB | IB | 25-6 | 22-11-21 | D04527J | | 8 | | SM00004 | | | 9 | ALL |
| 202R | 20 | | UB | IB | 0-0 | 22-11-21 | D04527J | | 7 | | SM00003 | | | 9 | ALL |
| 205B | 20 | | UB | IE | 0-6 | 22-11-21 | D00195 | | 7 | | SM00004 | | | 9 | ALL |
| 205R | 20 | | UB | IE | 0-0 | 22-11-21 | D00195 | | 8 | | SM00003 | | | 9 | ALL |
| 206B | 20 | | UB | IF | 0-6 | 22-11-21 | D00195 | | 12 | | SM00004 | | | 9 | ALL |
| 206R | 20 | | UB | IF | 0-0 | 22-11-21 | D00195 | | 13 | | SM00003 | | | 9 | ALL |
| 210B | 20 | | UB | IJ | 25-6 | 22-13-21 | D04527J | | 2 | | SM00008 | | | 9 | ALL |
| 210R | 20 | | UB | IJ | 0-0 | 22-13-21 | D04527J | | 1 | | SM00007 | | | 9 | ALL |
| 211B | 20 | | UB | IK | 0-6 | 22-13-21 | D00195 | | 6 | | SM00008 | | | 9 | ALL |
| 211R | 20 | | UB | IK | 0-0 | 22-13-21 | D00195 | | 5 | | SM00007 | | | 9 | ALL |
| 212B | 20 | | UB | IL | 0-6 | 22-13-21 | D00195 | | 4 | | SM00008 | | | 9 | ALL |
| 212R | 20 | | UB | IL | 0-0 | 22-13-21 | D00195 | | 3 | | SM00007 | | | 9 | ALL |
| 303B | 20 | | UC | MC | 25-6 | 22-13-21 | D04527J | | 11 | | D00195 | | 15 | | ALL |
| 303R | 20 | | UC | MC | 0-0 | 22-13-21 | D04527J | | 10 | | D00195 | | 16 | | ALL |
| 303Y | 20 | | UC | MC | 0-0 | 22-13-21 | D04527J | | 12 | | D00195 | | 14 | | ALL |
| 304B | 20 | | UC | MD | 25-6 | 22-13-21 | D04527J | | 14 | | D00195 | | 10 | | ALL |
| 304R | 20 | | UC | MD | 0-0 | 22-13-21 | D04527J | | 13 | | D00195 | | 11 | | ALL |
| 304Y | 20 | | UC | MD | 0-0 | 22-13-21 | D04527J | | 15 | | D00195 | | 9 | | ALL |
| 70K | 18 | | 5A | | 25-0 | 29-11-14 | D02087 | | 3 | | D04527J | 6 | DL | | ALL |
| 70L | 18 | | 5A | | 2-7 | 29-11-14 | D02087 | | 1 | | GD00755 | D.. | N | | ALL |
| 70M | 18 | | 5A | | 25-0 | 29-11-14 | D02087 | | 2 | | D04527J | 5 | DL | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0590

Page 17 End

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0600 | 286T0600 | | | ANTISKID AND OXYGEN PRESSURE INDICATION | | | | | | | | | | | |
| 001 | 24 | | PK | | 22-6 | 32-42-11 | D04772P | | | | D04874J | | | | ALL |
| 002 | 24 | | PK | | 22-6 | 32-42-11 | D04772P | | | | D04874J | | | | ALL |
| 007 | 24 | | PK | | 12-0 | 35-11-13 | D04772P | | | | D00752 | | A | | ALL |
| 012 | 20 | | PA | | 3-0 | 35-11-13 | GD03078 | D.. | E | | D00752 | | D | | ALL |
| 020 | 20 | | PA | | 22-6 | SPARE | D04772P | | | | D04874J | | | | ALL |
| 201B | 24 | | PL | A | 12-0 | 35-11-13 | D00752 | | | | D04772P | | | | ALL |
| 201R | 24 | | PL | A | 0-0 | 35-11-13 | D00752 | | | | D04772P | | | | ALL |
| W0602 | 286T0602 | | | LANDING GEAR POSITION INDICATION & ANTISKID | | | | | | | | | | | |
| 001R | 22 | | PH | | 52-7 | 26-17-11 | SP01522 | | | | D05044J | | | | ALL |
| 003R | 22 | | PH | | 76-6 | 26-18-31 | D04932P | | | | D05044J | | | | 050-099 |
| 003R | 22 | | PH | | 86-4 | 26-18-31 | D04932P | | | | D05044J | | | | 150-199, 275-299 |
| 004R | 22 | | PH | | 48-8 | 26-18-11 | D04932P | | | | D04484J | | | | 050-099 |
| 004R | 22 | | PH | | 59-0 | 26-18-11 | D04932P | | | | D04484J | | | | 150-199, 275-299 |
| 005 | 22 | | PA | | 59-0 | SPARE | D04932P | | | | D04484J | | CAP | Y | 150-155, 162-165, 275-276 |
| 005 | 22 | | PA | | 59-0 | SPARE | D04932P | | | | D04484J | | | | 156-157, 166-199, 277-299 |
| 006 | 22 | | PA | | 59-0 | SPARE | D04932P | | | | D04484J | | | | 150-199, 275-299 |
| 007 | 22 | | PA | | 59-0 | SPARE | D04932P | | | | D04484J | | | | 150-199, 275-299 |
| 008 | 20 | | PA | | 54-4 | SPARE | D04484J | | | | D04930J | | | | 150-199, 275-299 |
| 009 | 20 | | PA | | 43-11 | SPARE | D04484J | | | | D04930J | | | | 050-099 |
| 009 | 20 | | PA | | 54-4 | SPARE | D04484J | | | | D04930J | | | | 150-199, 275-299 |
| 010 | 20 | | PA | | 43-11 | SPARE | D04484J | | | | D04930J | | | | 050-099 |
| 010 | 20 | | PA | | 54-4 | SPARE | D04484J | | | | D04930J | | | | 150-199, 275-299 |
| 011 | 24 | | PK | | 2-5 | 32-42-11 | D05554J | | | | D04930J | | | | 050-099 |
| 011 | 24 | | PK | | 2-7 | 32-42-11 | D05554J | | | | D04930J | | | | 150-199, 275-299 |
| 012 | 22 | | PA | | 71-8 | 32-42-11 | D04930J | | | | D04598J | | | | 050-099 |
| 012 | 22 | | PA | | 81-8 | 32-42-11 | D04930J | | | | D04598J | | | | 150-199, 275-299 |
| 013 | 20 | | PA | | 3-7 | 32-42-11 | GD00668 | D.. | 2 | | D04598J | | | | ALL |
| 014 | 22 | | PA | | 71-8 | 32-42-11 | D04930J | | | | D04598J | | | | 050-099 |
| 014 | 22 | | PA | | 81-8 | 32-42-11 | D04930J | | | | D04598J | | | | 150-199, 275-299 |
| 015 | 20 | | PA | | 3-7 | 32-42-11 | GD00668 | D.. | 2 | | D04598J | | | | ALL |
| 016 | 22 | | PA | | 71-8 | 32-42-11 | D04930J | | | | D04598J | | | | 050-099 |
| 016 | 22 | | PA | | 81-8 | 32-42-11 | D04930J | | | | D04598J | | | | 150-199, 275-299 |
| 017 | 20 | | PA | | 3-7 | 32-42-11 | GD00668 | D.. | 2 | | D04598J | | | | ALL |
| 018R | 22 | | PH | | 76-6 | 26-17-11 | D04932P | | | | D05044J | | | | 050-099 |
| 018R | 22 | | PH | | 86-4 | 26-17-11 | D04932P | | | | D05044J | | | | 150-199, 275-299 |
| 019 | 20 | | PA | | 59-4 | SPARE | D05058J | | | | D04932P | | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0602 | 286T0602 | | | LANDING GEAR POSITION INDICATION & ANTISKID (continued) | | | | | | | | | | | | | |
| 020 | 20 | | PA | 59-4 | SPARE | D05058J | 6 | | | | | | D04932P | 9 | | | 150-199, 275-299 |
| 021 | 20 | | PA | 49-0 | SPARE | D05058J | 7 | | | | | | D04932P | 10 | | | 050-099 |
| 021 | 20 | | PA | 59-4 | SPARE | D05058J | 7 | | | | | | D04932P | 10 | | | 150-199, 275-299 |
| 022 | 20 | | PA | 52-1 | 33-42-21 | D04932P | 12 | | | | | | D02112 | 3 | | | 050-099 |
| 022 | 18 | | PA | 61-11 | 33-42-21 | D04932P | 12 | | DL | | | | D02112 | 3 | | | 150-199, 275-299 |
| 024 | 24 | | PK | 49-0 | 21-51-11 | D04932P | 13 | | | | | | D05058J | 1 | | | 050-099 |
| 024 | 24 | | PK | 59-4 | 21-51-11 | D04932P | 13 | | | | | | D05058J | 1 | | | 150-199, 275-299 |
| 025 | 24 | | PK | 49-0 | 21-51-11 | D04932P | 14 | | | | | | D05058J | 2 | | | 050-099 |
| 025 | 24 | | PK | 59-4 | 21-51-11 | D04932P | 14 | | | | | | D05058J | 2 | | | 150-199, 275-299 |
| 026 | 24 | | PK | 49-0 | 21-51-11 | D04932P | 16 | | | | | | D05058J | 3 | | | 050-099 |
| 026 | 24 | | PK | 59-4 | 21-51-11 | D04932P | 16 | | | | | | D05058J | 3 | | | 150-199, 275-299 |
| 027 | 24 | | PK | 49-0 | 21-51-11 | D04932P | 17 | | | | | | D05058J | 4 | | | 050-099 |
| 027 | 24 | | PK | 59-4 | 21-51-11 | D04932P | 17 | | | | | | D05058J | 4 | | | 150-199, 275-299 |
| 028 | 20 | | PA | 52-2 | SPARE | D05058J | 12 | | | | | | D05364J | 14 | | | 050-099 |
| 028 | 20 | | PA | 62-1 | SPARE | D05058J | 12 | | | | | | D05364J | 14 | | | 150-199, 275-299 |
| 029 | 20 | | PA | 52-2 | SPARE | D05058J | 13 | | | | | | D05364J | 13 | | | 050-099 |
| 029 | 20 | | PA | 62-1 | SPARE | D05058J | 13 | | | | | | D05364J | 13 | | | 150-199, 275-299 |
| 030 | 24 | | PK | 49-0 | SPARE | D04932P | 32 | | | | | | D05058J | 9 | | | 050-099 |
| 030 | 24 | | PK | 59-4 | 21-51-11 | D04932P | 32 | | | | | | D05058J | 9 | | | 150-199, 275-299 |
| 031 | 22 | | PQ | L | 51-10 | 29-33-11 | 11 | | | | | | D04484J | 53 | | | 050-099 |
| 031 | 22 | | PQ | L | 61-10 | 29-33-11 | 11 | | | | | | D04484J | 53 | | | 150-199, 275-299 |
| 031Z | | | L | | 0-0 | 29-33-11 | | | | FA | | | D04484J | | | FB | ALL |
| 032 | 22 | | PA | 51-10 | 29-33-11 | D05364J | 3 | | | | | | D04484J | 43 | | | 050-099 |
| 032 | 22 | | PA | 61-10 | 29-33-11 | D05364J | 3 | | | | | | D04484J | 43 | | | 150-199, 275-299 |
| 033 | 22 | | PA | 51-10 | 29-33-11 | D05364J | 4 | | | | | | D04484J | 44 | | | 050-099 |
| 033 | 22 | | PA | 61-10 | 29-33-11 | D05364J | 4 | | | | | | D04484J | 44 | | | 150-199, 275-299 |
| 034 | 22 | | PA | 51-10 | 29-33-11 | D05364J | 5 | | | | | | D04484J | 45 | | | 050-099 |
| 034 | 22 | | PA | 61-10 | 29-33-11 | D05364J | 5 | | | | | | D04484J | 45 | | | 150-199, 275-299 |
| 035 | 22 | | PA | 76-5 | 29-31-11 | D04932P | 24 | | | | | | D04598J | 10 | | | 050-099 |
| 035 | 22 | | PA | 86-4 | 29-31-11 | D04932P | 24 | | | | | | D04598J | 10 | | | 150-199, 275-299 |
| 038 | 24 | | PK | 48-8 | 29-32-11 | D04932P | 27 | | | | | | D04484J | 36 | | | 050-099 |
| 038 | 24 | | PK | 59-0 | 29-32-11 | D04932P | 27 | | | | | | D04484J | 36 | | | 150-199, 275-299 |
| 040 | 22 | | PA | 22-2 | SPARE | D05364J | 15 | | | | | | D05780P | 32 | | | 050-099 |
| 040 | 22 | | PA | 22-1 | SPARE | D05364J | 15 | | | | | | D05780P | 32 | | | 150-157, 163-199, 275-299 |
| 040 | 22 | | PA | 22-1 | SPARE | D05364J | 15 | | | | | | D05780P | CAP | Y | | 162 |
| 041 | 20 | | PA | 59-9 | SPARE | D05058J | 8 | | | | | | D05780P | 38 | | | 150-154, 275 |
| 042 | 20 | | PA | 86-9 | SPARE | D05044J | 7 | | | | | | D05780P | 39 | | | 150-154, 275 |
| 043 | 20 | | PA | 86-9 | SPARE | D04598J | 13 | | | | | | D05780P | 40 | | | 150-154, 275 |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0602 | 286T0602 | | | LANDING GEAR POSITION INDICATION & ANTISKID (continued) | | | | | | | | | | | |
| 044 | 20 | | PA | 86-9 | SPARE | D04598J | 14 | | | | D05780P | 41 | | | 150-154, 275 |
| 048 | 24 | | PK | 48-8 | 29-32-11 | D04484J | 37 | | | | D04932P | 30 | | | 050-099 |
| 048 | 24 | | PK | 59-0 | 29-32-11 | D04484J | 37 | | | | D04932P | 30 | | | 150-199, 275-299 |
| 049 | 20 | | PA | 76-8 | SPARE | D04302J | 1 | | | | D05780P | 4 | | | 050-099 |
| 049 | 22 | | PA | 15-2 | 32-71-11 | D05554J | 4 | | | | D05780P | 4 | | | 150-199, 275-299 |
| 079 | 18 | | PA | 52-3 | 33-42-11 | D04932P | 51 | DL | | | T00129 | HV3 | E | | 050-099 |
| 079 | 16 | | PA | 62-1 | 33-42-11 | D04932P | 15 | FL | | | T00129 | HV3 | E | | 150-199, 275-299 |
| 080 | 20 | | PA | 52-3 | 33-42-11 | D04932P | 52 | | | | T00129 | HV1 | E | | 050-099 |
| 080 | 16 | | PA | 62-1 | 33-42-11 | D04932P | 52 | FL | | | T00129 | HV1 | E | | 150-199, 275-299 |
| 081 | 12 | | PA | 3-2 | 33-42-11 | GD04190 | A.. | E | | | T00129 | GND | E | | ALL |
| 082 | 12 | | PA | 13-11 | 33-42-11 | L00111 | =P | M | | | T00129 | LV | E | | ALL |
| 083 | 12 | | PA | 2-10 | 33-42-11 | L00111 | =G | M | | | GD01450 | A.. | N | | ALL |
| 084 | 24 | | PK | 48-8 | 36-11-51 | D04932P | 1 | | | | D04484J | 19 | | | 050-099 |
| 084 | 24 | | PK | 59-0 | 36-11-51 | D04932P | 1 | | | | D04484J | 19 | | | 150-199, 275-299 |
| 085 | 18 | | PA | 48-8 | SPARE | D04932P | 40 | | | | D04484J | 21 | DK | | 050-099 |
| 085 | 18 | | PA | 59-0 | SPARE | D04932P | 40 | | | | D04484J | 21 | DK | | 150-199, 275-299 |
| 086 | 24 | | PK | 48-8 | 36-11-51 | D04932P | 22 | | | | D04484J | 23 | | | 050-099 |
| 086 | 24 | | PK | 59-0 | 36-11-51 | D04932P | 22 | | | | D04484J | 23 | | | 150-199, 275-299 |
| 087 | 24 | | PK | 49-0 | 36-23-11 | D05780P | 12 | | | | D04484J | 25 | | | 050-099 |
| 087 | 24 | | PK | 59-5 | 36-23-11 | D05780P | 12 | | | | D04484J | 25 | | | 150-199, 275-299 |
| 088 | 24 | | PK | 48-8 | 36-11-51 | D04932P | 53 | | | | D04484J | 24 | | | 050-099 |
| 088 | 24 | | PK | 59-0 | 36-11-51 | D04932P | 53 | | | | D04484J | 24 | | | 150-199, 275-299 |
| 089 | 18 | | PA | 48-8 | 36-11-51 | D04932P | 54 | DL | | | D04484J | 22 | DK | | 050-099 |
| 089 | 18 | | PA | 59-0 | 36-11-51 | D04932P | 54 | DL | | | D04484J | 22 | DK | | 150-199, 275-299 |
| 090 | 18 | | PA | 48-8 | 36-11-51 | D04932P | 56 | | | | D04484J | 20 | DK | | 050-099 |
| 090 | 18 | | PA | 59-0 | 36-11-51 | D04932P | 56 | | | | D04484J | 20 | DK | | 150-199, 275-299 |
| 091 | 24 | | PK | 48-8 | 36-11-51 | D04932P | 57 | | | | D04484J | 18 | | | 050-099 |
| 091 | 24 | | PK | 59-0 | 36-11-51 | D04932P | 57 | | | | D04484J | 18 | | | 150-199, 275-299 |
| 093 | 24 | | PK | 49-0 | 36-11-61 | D05780P | 1 | | | | D04484J | 1 | | | 050-099 |
| 093 | 24 | | PK | 59-5 | 36-11-61 | D05780P | 1 | | | | D04484J | 1 | | | 150-199, 275-299 |
| 094 | 24 | | PK | 49-0 | 36-11-61 | D05780P | 2 | | | | D04484J | 2 | | | 050-099 |
| 094 | 24 | | PK | 59-5 | 36-11-61 | D05780P | 2 | | | | D04484J | 2 | | | 150-199, 275-299 |
| 095 | 18 | | PA | 49-0 | 36-11-61 | D05780P | 3 | DK | | | D04484J | 3 | DK | | 050-099 |
| 095 | 18 | | PA | 59-5 | 36-11-61 | D05780P | 3 | DK | | | D04484J | 3 | DK | | 150-199, 275-299 |
| 096 | 18 | | PA | 49-0 | 36-11-61 | D05780P | 5 | DK | | | D04484J | 5 | DK | | 050-099 |
| 096 | 18 | | PA | 59-5 | 36-11-61 | D05780P | 5 | DK | | | D04484J | 5 | DK | | 150-199, 275-299 |
| 097 | 24 | | PK | 49-0 | 36-11-61 | D05780P | 6 | | | | D04484J | 6 | | | 050-099 |
| 097 | 24 | | PK | 59-5 | 36-11-61 | D05780P | 6 | | | | D04484J | 6 | | | 150-199, 275-299 |
| 098 | 24 | | PK | 49-0 | 36-11-61 | D05780P | 7 | | | | D04484J | 7 | | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0600
Page 3
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0602 | 286T0602 | | | LANDING GEAR POSITION INDICATION & ANTISKID (continued) | | | | | | | | | | | | | |
| 098 | 24 | | PK | 59-5 | 36-11-61 | D05780P | | 7 | | | | | D04484J | | 7 | | 150-199, 275-299 |
| 099 | 24 | | PK | 49-0 | 36-11-61 | D05780P | | 8 | | | | | D04484J | | 8 | | 050-099 |
| 099 | 24 | | PK | 59-5 | 36-11-61 | D05780P | | 8 | | | | | D04484J | | 8 | | 150-199, 275-299 |
| 101 | 24 | | PK | 49-0 | 36-11-61 | D05780P | | 10 | | | | | D04484J | | 10 | | 050-099 |
| 101 | 24 | | PK | 59-5 | 36-11-61 | D05780P | | 10 | | | | | D04484J | | 10 | | 150-199, 275-299 |
| 102 | 20 | | PA | 76-8 | SPARE | D04302J | | 2 | | | | | D05780P | | 9 | | 050-099 |
| 102 | 20 | | PA | 86-7 | SPARE | D04302J | | 2 | | | | | D05780P | | 9 | | 150-199, 275-299 |
| 103 | 24 | | PK | 49-0 | 36-23-11 | D05780P | | 13 | | | | | D04484J | | 33 | | 050-099 |
| 103 | 24 | | PK | 59-5 | 36-23-11 | D05780P | | 13 | | | | | D04484J | | 33 | | 150-199, 275-299 |
| 104 | 24 | | PK | 49-0 | 36-23-11 | D05780P | | 14 | | | | | D04484J | | 32 | | 050-099 |
| 104 | 24 | | PK | 59-5 | 36-23-11 | D05780P | | 14 | | | | | D04484J | | 32 | | 150-199, 275-299 |
| 105 | 24 | | PK | 49-0 | 36-23-11 | D05780P | | 15 | | | | | D04484J | | 26 | | 050-099 |
| 105 | 24 | | PK | 59-5 | 36-23-11 | D05780P | | 15 | | | | | D04484J | | 26 | | 150-199, 275-299 |
| 106 | 24 | | PK | 49-0 | 36-23-11 | D05780P | | 16 | | | | | D04484J | | 27 | | 050-099 |
| 106 | 24 | | PK | 59-5 | 36-23-11 | D05780P | | 16 | | | | | D04484J | | 27 | | 150-199, 275-299 |
| 107 | 24 | | PK | 49-0 | 36-11-61 | D05780P | | 33 | | | | | D04484J | | 40 | | 050-099 |
| 107 | 24 | | PK | 59-5 | 36-11-61 | D05780P | | 33 | | | | | D04484J | | 40 | | 150-199, 275-299 |
| 108 | 24 | | PK | 49-0 | 36-11-61 | D05780P | | 34 | | | | | D04484J | | 41 | | 050-099 |
| 108 | 24 | | PK | 59-5 | 36-11-61 | D05780P | | 34 | | | | | D04484J | | 41 | | 150-199, 275-299 |
| 111 | 20 | | PA | 15-2 | SPARE | D05780P | | 21 | | | | | D05554J | | 22 | | ALL |
| 112 | 20 | | PA | 15-2 | SPARE | D05780P | | 22 | | | | | D05554J | | 23 | | 050-099, 150-157, 163-199, 275-299 |
| 112 | 20 | | PA | 15-2 | SPARE | D05780P | | CAP | Y | | | | D05554J | | 23 | | 162 |
| 114 | 22 | | PA | 76-5 | 28-42-11 | D04932P | | 2 | | | | | D04598J | | 8 | | 050-099 |
| 114 | 22 | | PA | 86-4 | 28-42-11 | D04932P | | 2 | | | | | D04598J | | 8 | | 150-199, 275-299 |
| 115 | 22 | | PA | 76-5 | 28-42-31 | D04932P | | 28 | | | | | D04598J | | 9 | | 050-099 |
| 115 | 22 | | PA | 86-4 | 28-42-31 | D04932P | | 28 | | | | | D04598J | | 9 | | 150-199, 275-299 |
| 116 | 16 | | PA | 7-2 | 33-42-21 | D02112 | | 1 | | | | | GD03554 | A.. | 2 | | ALL |
| 117 | 16 | | PA | 7-2 | 33-42-21 | D02112 | | 6 | | | | | GD03554 | S.. | 2 | | ALL |
| 118 | 16 | | PA | 13-4 | 33-42-21 | D02112 | | 5 | | | | | L00115 | =P | M | | ALL |
| 119 | 16 | | PA | 2-5 | 33-42-21 | GD01450 | | A.. | N | | | | L00115 | =G | M | | ALL |
| 120 | 24 | | PK | 76-5 | 36-11-31 | D05556J | | 3 | | | | | D04932P | | 19 | | 050-099 |
| 120 | 24 | | PK | 86-3 | 36-11-31 | D05556J | | 3 | | | | | D04932P | | 19 | | 150-199, 275-299 |
| 121 | 24 | | PK | 76-5 | 36-11-31 | D05556J | | 4 | | | | | D04932P | | 20 | | 050-099 |
| 121 | 24 | | PK | 86-3 | 36-11-31 | D05556J | | 4 | | | | | D04932P | | 20 | | 150-199, 275-299 |
| 122 | 24 | | PV | N | 76-5 | 36-11-31 | D05556J | | 5 | | | | D04932P | | 21 | | 050-099 |
| 122 | 24 | | PV | N | 86-3 | 36-11-31 | D05556J | | 5 | | | | D04932P | | 21 | | 150-199, 275-299 |
| 122Z | | | | N | 0-0 | 36-11-31 | D05556J | | DED | | | | D04932P | | DED | | ALL |
| 123 | 24 | | PV | O | 76-5 | 36-11-31 | D05556J | | 6 | | | | D04932P | | 29 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0602 | 286T0602 | | | LANDING GEAR POSITION INDICATION & ANTISKID (continued) | | | | | | | | | | | |
| 123 | 24 | PV | O | 86-3 | 36-11-31 | D05556J | 6 | | | D04932P | 29 | | | 150-199, 275-299 | |
| 123Z | | | O | 0-0 | 36-11-31 | D05556J | DED | | | D04932P | DED | | | ALL | |
| 124 | 20 | PA | | 3-7 | 36-11-31 | D05556J | 7 | | | GD00668 | D.. | 2 | | ALL | |
| 125 | 20 | PA | | 3-7 | 36-11-31 | D05556J | 8 | | | GD00668 | D.. | 2 | | ALL | |
| 126 | 20 | PA | | 3-7 | 36-11-31 | D05556J | 9 | | | GD00668 | A.. | 2 | | ALL | |
| 129 | 16 | PA | | 5-1 | 25-65-11 | D04598J | 15 | | | SP01638 | | 9 | | ALL | |
| 130 | 16 | PA | | 3-7 | 25-65-11 | D04598J | 16 | | | GD00668 | D.. | 2 | | ALL | |
| 135 | 22 | PA | | 48-8 | 29-32-11 | D04932P | 18 | | | D04484J | 46 | | | 050-099 | |
| 135 | 22 | PA | | 59-0 | 29-32-11 | D04932P | 18 | | | D04484J | 46 | | | 150-199, 275-299 | |
| 136 | 22 | PA | | 49-0 | 29-11-12 | D05780P | 29 | | | D04484J | 51 | | | 050-099 | |
| 136 | 22 | PA | | 59-5 | 29-11-12 | D05780P | 29 | | | D04484J | 51 | | | 150-199, 275-299 | |
| 141 | 24 | PV | P | 2-5 | 32-42-11 | D05554J | 15 | | | D04930J | 15 | | | 050-099 | |
| 141 | 24 | PV | P | 2-7 | 32-42-11 | D05554J | 15 | | | D04930J | 15 | | | 150-199, 275-299 | |
| 141Z | | | P | 0-0 | 32-42-11 | D05554J | DED | | | D04930J | DED | | | ALL | |
| 156 | 24 | PK | | 49-0 | 36-11-61 | D05780P | 23 | | | D04484J | 42 | | | 050-099 | |
| 156 | 24 | PK | | 59-5 | 36-11-61 | D05780P | 23 | | | D04484J | 42 | | | 150-157, 163-199, 275-299 | |
| 156 | 24 | PK | | 59-5 | 36-11-61 | D05780P | 22 | | | D04484J | 42 | | | 162 | |
| 191 | 24 | PK | | 49-0 | 36-11-61 | D05780P | 25 | | | D04484J | 9 | | | 050-099 | |
| 191 | 24 | PK | | 59-5 | 36-11-61 | D05780P | 25 | | | D04484J | 9 | | | 150-199, 275-299 | |
| 192B | 24 | PL | AT | 49-0 | 36-11-61 | D05780P | 27 | | | D04484J | 49 | | | 050-099 | |
| 192B | 24 | PL | AT | 59-5 | 36-11-61 | D05780P | 27 | | | D04484J | 49 | | | 150-157, 163-199, 275-299 | |
| 192B | 24 | PL | AT | 59-5 | 36-11-61 | D05780P | 32 | | | D04484J | 49 | | | 162 | |
| 192R | 24 | PL | AT | 0-0 | 36-11-61 | D05780P | 26 | | | D04484J | 50 | | | ALL | |
| 201B | 22 | PB | C | 15-2 | SPARE | D05554J | 30 | | | D05780P | 35 | | | 150-154, 275 | |
| 201R | 22 | PB | C | 0-0 | SPARE | D05554J | 31 | | | D05780P | 36 | | | 150-154, 275 | |
| 203B | 22 | PB | K | 72-0 | 32-09-11 | D04302J | 6 | | | D05554J | 6 | | | 050-099 | |
| 203B | 22 | PB | K | 82-1 | 32-09-11 | D04302J | 6 | | | D05554J | 6 | | | 150-199, 275-299 | |
| 203R | 22 | PB | K | 0-0 | 32-09-11 | D04302J | 5 | | | D05554J | 5 | | | ALL | |
| 204B | 22 | PB | B | 72-1 | 32-61-11 | D05554J | 2 | | | D05556J | 2 | | | 050-099 | |
| 204B | 22 | PB | B | 82-2 | 32-61-11 | D05554J | 2 | | | D05556J | 2 | | | 150-199, 275-299 | |
| 204R | 22 | PB | B | 0-0 | 32-61-11 | D05554J | 1 | | | D05556J | 1 | | | ALL | |
| 206B | 22 | PB | D | 72-0 | 32-61-11 | D05554J | 8 | | | D04302J | 8 | | | 050-099 | |
| 206B | 22 | PB | D | 82-1 | 32-61-11 | D05554J | 8 | | | D04302J | 8 | | | 150-199, 275-299 | |
| 206R | 22 | PB | D | 0-0 | 32-61-11 | D05554J | 7 | | | D04302J | 7 | | | ALL | |
| 207B | 22 | PB | E | 72-0 | 32-61-11 | D05554J | 10 | | | D04302J | 10 | | | 050-099 | |
| 207B | 22 | PB | E | 82-1 | 32-61-11 | D05554J | 10 | | | D04302J | 10 | | | 150-199, 275-299 | |
| 207R | 22 | PB | E | 0-0 | 32-61-11 | D05554J | 9 | | | D04302J | 9 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 5

Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0602 | 286T0602 | | | LANDING GEAR POSITION INDICATION & ANTISKID (continued) | | | | | | | | | | | | |
| 208B | 20 | PR | G | 71-6 | 32-42-11 | D04930J | | 17 | | | | D04302J | 17 | | 050-099 | |
| 208B | 20 | PR | G | 81-6 | 32-42-11 | D04930J | | 17 | | | | D04302J | 17 | | 150-199, 275-299 | |
| 208R | 20 | PR | G | 0-0 | 32-42-11 | D04930J | | 13 | | | | D04302J | 13 | | ALL | |
| 208Z | | | G | 0-0 | 32-42-11 | D04930J | | 20 | | | | D04302J | 3 | | ALL | |
| 209B | 20 | PR | H | 71-6 | 32-42-11 | D04930J | | 19 | | | | D04302J | 19 | | 050-099 | |
| 209B | 20 | PR | H | 81-6 | 32-42-11 | D04930J | | 19 | | | | D04302J | 19 | | 150-199, 275-299 | |
| 209R | 20 | PR | H | 0-0 | 32-42-11 | D04930J | | 18 | | | | D04302J | 18 | | ALL | |
| 209Z | | | H | 0-0 | 32-42-11 | D04930J | | 21 | | | | D04302J | 4 | | ALL | |
| 210B | 20 | PB | R | 48-8 | 36-22-21 | D04932P | | 42 | | | | D04484J | 39 | | 050-099 | |
| 210B | 20 | PB | R | 59-0 | 36-22-21 | D04932P | | 42 | | | | D04484J | 39 | | 150-199, 275-299 | |
| 210R | 20 | PB | R | 0-0 | 36-22-21 | D04932P | | 41 | | | | D04484J | 38 | | ALL | |
| 211B | 22 | PB | A | 76-5 | 29-31-11 | D04932P | | 26 | | | | D04598J | 12 | | 050-099 | |
| 211B | 22 | PB | A | 86-4 | 29-31-11 | D04932P | | 26 | | | | D04598J | 12 | | 150-199, 275-299 | |
| 211R | 22 | PB | A | 0-0 | 29-31-11 | D04932P | | 25 | | | | D04598J | 11 | | ALL | |
| 237B | 24 | PL | JL | 49-4 | 21-51-11 | D05780P | | 30 | | | | D05058J | 10 | | 050-099 | |
| 237B | 24 | PL | JL | 59-9 | 21-51-11 | D05780P | | 30 | | | | D05058J | 10 | | 150-199, 275-299 | |
| 237R | 24 | PL | JL | 0-0 | 21-51-11 | D05780P | | 31 | | | | D05058J | 11 | | ALL | |
| 241B | 20 | PR | JA | 71-9 | 32-45-13 | D06756J | | 1 | | | | D06340J | 9 | | 050-099 | |
| 241B | 20 | PR | JA | 81-10 | 32-45-13 | D06756J | | 1 | | | | D06340J | 9 | | 150-199 | |
| 241B | 20 | PR | JA | 90-4 | 32-45-13 | D06806J | | 1 | | | | D06340J | 9 | | 275-299 | |
| 241R | 20 | PR | JA | 0-0 | 32-45-13 | D06756J | | 2 | | | | D06340J | 10 | | 050-099, 150-199 | |
| 241R | 20 | PR | JA | 0-0 | 32-45-13 | D06806J | | 2 | | | | D06340J | 10 | | 275-299 | |
| 241Z | | | JA | 0-0 | 32-45-13 | D06756J | | 3 | | | | D06340J | 11 | | 050-099, 150-199 | |
| 241Z | | | JA | 0-0 | 32-45-13 | D06806J | | 3 | | | | D06340J | 11 | | 275-299 | |
| 242B | 20 | PR | JB | 71-9 | 32-45-13 | D06756J | | 4 | | | | D06340J | 12 | | 050-099 | |
| 242B | 20 | PR | JB | 81-10 | 32-45-13 | D06756J | | 4 | | | | D06340J | 12 | | 150-199 | |
| 242B | 20 | PR | JB | 90-4 | 32-45-13 | D06806J | | 4 | | | | D06340J | 12 | | 275-299 | |
| 242R | 20 | PR | JB | 0-0 | 32-45-13 | D06756J | | 5 | | | | D06340J | 13 | | 050-099, 150-199 | |
| 242R | 20 | PR | JB | 0-0 | 32-45-13 | D06806J | | 5 | | | | D06340J | 13 | | 275-299 | |
| 242Z | | | JB | 0-0 | 32-45-13 | D06756J | | 6 | | | | D06340J | 14 | | 050-099, 150-199 | |
| 242Z | | | JB | 0-0 | 32-45-13 | D06806J | | 6 | | | | D06340J | 14 | | 275-299 | |
| 243B | 20 | PR | JC | 71-8 | 32-45-13 | D06756J | | 7 | | | | D08268J | 8 | | 050-099 | |
| 243B | 20 | PR | JC | 81-8 | 32-45-13 | D06756J | | 7 | | | | D08268J | 8 | | 150-199 | |
| 243B | 20 | PR | JC | 90-2 | 32-45-13 | D06806J | | 7 | | | | D08268J | 8 | | 275-299 | |
| 243R | 20 | PR | JC | 0-0 | 32-45-13 | D06756J | | 8 | | | | D08268J | 9 | | 050-099, 150-199 | |
| 243R | 20 | PR | JC | 0-0 | 32-45-13 | D06806J | | 8 | | | | D08268J | 9 | | 275-299 | |
| 243Z | | | JC | 0-0 | 32-45-13 | D06756J | | 9 | | | | D08268J | 10 | | 050-099, 150-199 | |
| 243Z | | | JC | 0-0 | 32-45-13 | D06806J | | 9 | | | | D08268J | 10 | | 275-299 | |
| 244B | 20 | PR | JD | 71-8 | 32-45-13 | D06756J | | 10 | | | | D08268J | 11 | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0602 | 286T0602 | | | LANDING GEAR POSITION INDICATION & ANTISKID (continued) | | | | | | | | | | | |
| 244B | 20 | PR | JD | 81-8 | 32-45-13 | D06756J | 10 | | | D08268J | 11 | | | 150-199 | |
| 244B | 20 | PR | JD | 90-2 | 32-45-13 | D06806J | 10 | | | D08268J | 11 | | | 275-299 | |
| 244R | 20 | PR | JD | 0-0 | 32-45-13 | D06756J | 11 | | | D08268J | 12 | | | 050-099, 150-199 | |
| 244R | 20 | PR | JD | 0-0 | 32-45-13 | D06806J | 11 | | | D08268J | 12 | | | 275-299 | |
| 244Z | | | JD | 0-0 | 32-45-13 | D06756J | 12 | | | D08268J | 13 | | | 050-099, 150-199 | |
| 244Z | | | JD | 0-0 | 32-45-13 | D06806J | 12 | | | D08268J | 13 | | | 275-299 | |
| 301B | 24 | PX | M | 49-0 | 36-23-11 | D05780P | 18 | | | D04484J | 28 | | | 050-099 | |
| 301B | 24 | PX | M | 59-5 | 36-23-11 | D05780P | 18 | | | D04484J | 28 | | | 150-199, 275-299 | |
| 301R | 24 | PX | M | 0-0 | 36-23-11 | D05780P | 19 | | | D04484J | 29 | | | ALL | |
| 301Y | 24 | PX | M | 0-0 | 36-23-11 | D05780P | 20 | | | D04484J | 30 | | | ALL | |
| 301Z | | | M | 0-0 | 36-23-11 | D05780P | 17 | | | D04484J | 31 | | | ALL | |
| 407R | 22 | PH | | 48-8 | 26-18-12 | D04932P | 34 | | | D04484J | 17 | | | 050-099 | |
| 407R | 22 | PH | | 59-0 | 26-18-12 | D04932P | 34 | | | D04484J | 17 | | | 150-199, 275-299 | |
| 408R | 22 | PH | | 48-8 | 26-18-12 | D04932P | 33 | | | D04484J | 11 | | | 050-099 | |
| 408R | 22 | PH | | 59-0 | 26-18-12 | D04932P | 33 | | | D04484J | 11 | | | 150-199, 275-299 | |
| 451G | 22 | XU | I | 78-1 | 32-46-11 | D04302J | 12 | 4H | | D05294J | 2 | 4E | | 050-099 | |
| 451G | 22 | XU | I | 88-1 | 32-46-11 | D04302J | 12 | 4H | | D05294J | 2 | 4E | | 150-199, 275-299 | |
| 451W | 22 | XU | I | 0-0 | 32-46-11 | D04302J | 11 | 4L | | D05294J | 1 | 4I | | ALL | |
| 452G | 22 | XU | J | 78-1 | 32-46-11 | D04302J | 15 | 4H | | D05294J | 4 | 4E | | 050-099 | |
| 452G | 22 | XU | J | 88-1 | 32-46-11 | D04302J | 15 | 4H | | D05294J | 4 | 4E | | 150-199, 275-299 | |
| 452W | 22 | XU | J | 0-0 | 32-46-11 | D04302J | 14 | 4L | | D05294J | 3 | 4I | | ALL | |
| 500 | 20 | PA | | 77-4 | 28-31-11 | D05780P | 37 | | | D08374J | 1 | | | 050-099 | |
| 500 | 20 | PA | | 87-3 | 28-31-11 | D05780P | 37 | | | D08374J | 1 | | | 155-199, 276-299 | |
| 501 | 20 | PA | | 77-4 | 28-31-11 | D05780P | 36 | | | D08374J | 2 | | | 050-099 | |
| 501 | 20 | PA | | 87-3 | 28-31-11 | D05780P | 36 | | | D08374J | 2 | | | 155-199, 276-299 | |
| 502 | 20 | PA | | 77-4 | 28-31-11 | D05780P | 35 | | | D08374J | 3 | | | 050-099 | |
| 502 | 20 | PA | | 87-3 | 28-31-11 | D05780P | 35 | | | D08374J | 3 | | | 155-199, 276-299 | |
| 503 | 20 | PA | | 77-4 | 28-31-12 | D05780P | 38 | | | D08374J | 4 | | | 050-099 | |
| 503 | 20 | PA | | 87-3 | 28-31-12 | D05780P | 38 | | | D08374J | 4 | | | 155-199, 276-299 | |
| 504 | 20 | PA | | 77-4 | 28-31-12 | D05780P | 39 | | | D08374J | 5 | | | 050-099 | |
| 504 | 20 | PA | | 87-3 | 28-31-12 | D05780P | 39 | | | D08374J | 5 | | | 155-199, 276-299 | |
| 505 | 20 | PA | | 77-4 | 28-31-12 | D05780P | 40 | | | D08374J | 6 | | | 050-099 | |
| 505 | 20 | PA | | 87-3 | 28-31-12 | D05780P | 40 | | | D08374J | 6 | | | 155-199, 276-299 | |
| 506 | 20 | PQ | UF | 77-4 | 28-42-13 | D05780P | 41 | | | D08374J | 7 | | | 050-099 | |
| 506 | 20 | PQ | UF | 87-3 | 28-42-13 | D05780P | 41 | | | D08374J | 7 | | | 155-199, 276-299 | |
| 506Z | | | UF | 0-0 | 28-42-13 | D05780P | DED | | | D08374J | DED | | | 050-099, 155-199, 276-299 | |
| FRA | | | | 0-0 | 29-33-11 | D05364J | | | FA | D05364J | 2 | | | ALL | |
| FRB | | | | 0-0 | 29-33-11 | D05364J | | | FA | D05364J | 10 | | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0600
Page 7
Mar 14/2007



| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | | | | |
|--------------|-----------------|--|----|--|----------|----------|---------|----|-----|-------|---------|-------|-------------|------|------|--------|-------|------------------|
| | | | | | Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | | Term | Type | Splice | Equip | Term |
| W0602 | 286T0602 | | | LANDING GEAR POSITION INDICATION & ANTISKID (continued) | | | | | | | | | | | | | | |
| FRC | | | | | 0-0 | 29-33-11 | D05364J | | | | | FA | D05364J | | 12 | | | ALL |
| FRD | | | | | 0-0 | 29-33-11 | D04484J | | | | | FB | D04484J | | 34 | | | ALL |
| FRE | | | | | 0-0 | 29-33-11 | D04484J | | | | | FB | D04484J | | 35 | | | ALL |
| FRF | | | | | 0-0 | 29-33-11 | D04484J | | | | | FB | D04484J | | 54 | | | ALL |
| W0603 | 286T0603 | | | PITCH SERVO ACTR | | | | | | | | | | | | | | |
| 001 | 20 | | UA | | 34-4 | 22-11-22 | D00197 | | | 2 | | | D04473J | | 1 | | | ALL |
| 002 | 20 | | UA | | 34-4 | 22-11-22 | D00197 | | | 18 | | | D04473J | | 14 | | | ALL |
| 003 | 18 | | UA | | 2-1 | 22-11-22 | D00197 | | | 17 | | | GD00161 | | D.. | N | | ALL |
| 004 | 18 | | UA | | 2-1 | 22-11-22 | D00197 | | | 1 | | | GD00161 | | D.. | N | | ALL |
| 005 | 18 | | UA | | 2-2 | 22-11-22 | D00197 | | | 19 | | | GD00163 | | S.. | N | | ALL |
| 006Y | 20 | | XP | | 4-7 | 27-41-21 | D04473J | | | 3 | | | SP00393 | | | | 9 | ALL |
| 201B | 20 | | UB | IA | 34-4 | 22-11-21 | D04473J | | | 5 | | | SM00002 | | | | 9 | ALL |
| 201R | 20 | | UB | IA | 0-0 | 22-11-21 | D04473J | | | 4 | | | SM00001 | | | | 9 | ALL |
| 203B | 20 | | UB | IC | 2-0 | 22-11-21 | D00197 | | | 7 | | | SM00002 | | | | 9 | ALL |
| 203R | 20 | | UB | IC | 0-0 | 22-11-21 | D00197 | | | 8 | | | SM00001 | | | | 9 | ALL |
| 204B | 20 | | UB | ID | 2-0 | 22-11-21 | D00197 | | | 12 | | | SM00002 | | | | 9 | ALL |
| 204R | 20 | | UB | ID | 0-0 | 22-11-21 | D00197 | | | 13 | | | SM00001 | | | | 9 | ALL |
| 207B | 20 | | UB | IG | 34-4 | 22-12-21 | D04473J | | | 10 | | | SM00006 | | | | 9 | ALL |
| 207R | 20 | | UB | IG | 0-0 | 22-12-21 | D04473J | | | 9 | | | SM00005 | | | | 9 | ALL |
| 208B | 20 | | UB | IH | 2-0 | 22-12-21 | D00197 | | | 3 | | | SM00006 | | | | 9 | ALL |
| 208R | 20 | | UB | IH | 0-0 | 22-12-21 | D00197 | | | 4 | | | SM00005 | | | | 9 | ALL |
| 209B | 20 | | UB | II | 2-0 | 22-12-21 | D00197 | | | 5 | | | SM00006 | | | | 9 | ALL |
| 209R | 20 | | UB | II | 0-0 | 22-12-21 | D00197 | | | 6 | | | SM00005 | | | | 9 | ALL |
| 301B | 20 | | UC | MA | 34-4 | 22-12-21 | D04473J | | | 12 | | | D00197 | | | 15 | | ALL |
| 301R | 20 | | UC | MA | 0-0 | 22-12-21 | D04473J | | | 11 | | | D00197 | | | 14 | | ALL |
| 301Y | 20 | | UC | MA | 0-0 | 22-12-21 | D04473J | | | 13 | | | D00197 | | | 16 | | ALL |
| 302B | 20 | | UC | MB | 34-4 | 22-12-21 | D04473J | | | 7 | | | D00197 | | | 10 | | ALL |
| 302R | 20 | | UC | MB | 0-0 | 22-12-21 | D04473J | | | 6 | | | D00197 | | | 9 | | ALL |
| 302Y | 20 | | UC | MB | 0-0 | 22-12-21 | D04473J | | | 8 | | | D00197 | | | 11 | | ALL |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION | | | | | | | | | | | | | | |
| 001R | 20 | | PH | | 15-3 | 26-22-21 | D04952P | | | 1 | | | D04948P | | | 1 | | 050-099 |
| 001R | 20 | | PH | | 15-1 | 26-22-21 | D04952P | | | 1 | | | D04948P | | | 1 | | 150-199, 275-299 |
| 002R | 20 | | PH | | 16-6 | 26-22-21 | D04948P | | | 2 | | | D04950J | | | 2 | | ALL |
| 003R | 22 | | PH | | 4-8 | 26-15-12 | D04950J | | | 13 | | | D03792 | | | B | | ALL |
| 004R | 20 | | PH | | 49-1 | 26-22-21 | SM00015 | | | | 9 | | SM00002 | | | 9 | | 050-099 |
| 004R | 20 | | PH | | 59-10 | 26-22-21 | SM00015 | | | | 9 | | SM00002 | | | 9 | | 150-199 |
| 004R | 20 | | PH | | 61-7 | 26-22-21 | D00846 | | | 23 | | | SM00002 | | | 9 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 8

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | | | | | |
|--------------|-----------------|----|-------|--|--------|----------|---------|-------|------|------|--------|-------|------|------|---------|-------------|-----|---|--|------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | | | | | | |
| 005R | 20 | | PH | | 39-7 | 26-22-21 | D04950J | | 4 | | | | | | SM00002 | | 9 | | | 050-099 |
| 005R | 20 | | PH | | 49-11 | 26-22-21 | D04950J | | 4 | | | | | | SM00002 | | 9 | | | 150-199, 275-299 |
| 006R | 20 | | PH | | 68-11 | 26-22-21 | D06110P | | 4 | | | | | | SM00002 | | 9 | | | 050-099 |
| 006R | 20 | | PH | | 79-6 | 26-22-21 | D06110P | | 4 | | | | | | SM00002 | | 9 | | | 150-199, 275-299 |
| 007R | 20 | | PH | | 20-8 | 26-22-21 | D04948P | | 19 | | | | | | SM00013 | | 9 | | | 050-099 |
| 007R | 20 | | PH | | 20-7 | 26-22-21 | D04948P | | 19 | | | | | | SM00013 | | 9 | | | 150-199, 275-299 |
| 008R | 20 | | PH | | 17-1 | 26-22-21 | D04952P | | 20 | | | | | | SM00014 | | 9 | | | 050-099 |
| 008R | 20 | | PH | | 16-10 | 26-22-21 | D04952P | | 20 | | | | | | SM00014 | | 9 | | | 150-199 |
| 008R | 20 | | PH | | 18-7 | 26-22-21 | D04952P | | 20 | | | | | | D00846 | | 22 | | | 275-299 |
| 009R | 20 | | PH | | 2-3 | 26-22-21 | D00866 | | 19 | | | | | | SM00013 | | 9 | | | ALL |
| 010R | 20 | | PH | | 29-0 | 26-22-21 | D04950J | | 11 | | | | | | SM00013 | | 9 | | | 050-099 |
| 010R | 20 | | PH | | 28-11 | 26-22-21 | D04950J | | 11 | | | | | | SM00013 | | 9 | | | 150-199, 275-299 |
| 011R | 20 | | PH | | 117-0 | 26-22-21 | D06110P | | 5 | | | | | | SM00013 | | 9 | | | 050-099 |
| 011R | 20 | | PH | | 137-10 | 26-22-21 | D06110P | | 5 | | | | | | SM00013 | | 9 | | | 150-199, 275-299 |
| 012R | 20 | | PH | | 2-2 | 26-11-11 | D10106 | | 2 | | | | | | GD04474 | | D.. | 2 | | ALL |
| 013R | 20 | | PH | | 13-6 | 26-22-21 | SP02480 | | | 9 | | | | | D04948P | | 10 | | | 275-299 |
| 014 | 20 | | PA | | 31-5 | 28-21-13 | SP01542 | | | S | | | | | D04652J | | 7 | | | 050-099 |
| 014 | 20 | | PA | | 32-0 | 28-21-13 | SP01542 | | | S | | | | | D04652J | | 7 | | | 150-199, 275-299 |
| 015 | 22 | | PA | | 31-5 | 28-21-13 | SP01528 | | | S | | | | | D04652J | | 6 | | | 050-099 |
| 015 | 22 | | PA | | 32-0 | 28-21-13 | SP01528 | | | S | | | | | D04652J | | 6 | | | 150-199, 275-299 |
| 019 | 20 | | PQ | AA | 28-3 | 28-22-21 | D00862 | | 32 | | | | | | SP01748 | | | S | | 050-099 |
| 019 | 20 | | PQ | AA | 29-1 | 28-22-21 | D00862 | | 32 | | | | | | SP01748 | | | S | | 150-154, 156-162, 165-199 |
| 019 | 20 | | PQ | AA | 9-8 | 28-22-21 | D00862 | | 32 | | | | | | SP09728 | | | S | | 155, 163-164, 275-299 |
| 019Z | | | | AA | 0-0 | 28-22-21 | D00862 | | DED | | | | | | SP01748 | | DED | | | 050-099, 150-154, 156-162, 165-199 |
| 019Z | | | | AA | 0-0 | 28-22-21 | D00862 | | DED | | | | | | SP09728 | | DED | | | 155, 163-164, 275-299 |
| 020 | 22 | | PA | | 68-4 | 31-31-22 | D04652J | | 12 | | | | | | D06594J | | 4 | | | 050-099 |
| 020 | 22 | | PA | | 78-8 | 31-31-22 | D04652J | | 12 | | | | | | D06594J | | 4 | | | 150-199 |
| 020 | 22 | | PA | | 78-8 | 31-31-22 | D06594J | | 4 | | | | | | D04652J | | 12 | | | 275-299 |
| 021 | 22 | | PA | | 19-3 | 31-31-22 | SP03262 | | | S | | | | | D06594J | | 5 | | | 050-099 |
| 021 | 22 | | PA | | 52-1 | 31-31-22 | SP03262 | | | S | | | | | D06594J | | 5 | | | 150-199 |
| 021 | 22 | | PA | | 52-1 | 31-31-22 | D06594J | | 5 | | | | | | SP03262 | | | S | | 275-299 |
| 022R | 20 | | PH | | 21-10 | 26-22-21 | D04950J | | 9 | | | | | | SP02480 | | | | | 275-299 |
| 023R | 20 | | PH | | 49-11 | 26-22-21 | D04950J | | 10 | | | | | | SM00004 | | | 9 | | 275-299 |
| 024 | 24 | | PK | | 104-9 | 31-31-22 | D05054J | | 1 | | | | | | D04948P | | 32 | | | 050-099 |
| 024 | 24 | | PK | | 125-4 | 31-31-22 | D05054J | | 1 | | | | | | D04948P | | 32 | | | 150-199 |
| 024 | 24 | | PK | | 125-4 | 31-31-22 | D05054J | | 1 | | | | | | D04948P | | 46 | | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0600
Page 9
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | | | |
| 025R | 20 | | PH | 6-0 | 26-16-11 | D06944P | | 7 | | | | | GD00106 | S.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 025R | 20 | | PH | 7-7 | 26-16-11 | D06944P | | 7 | | | | | GD00106 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 026R | 24 | | PP | 15-6 | 26-16-11 | D04952P | | 7 | | | | | D07994P | 31 | | | 050-099 |
| 026R | 24 | | PP | 15-4 | 26-16-11 | D04952P | | 7 | | | | | D07994P | 31 | | | 150-199, 275-299 |
| 027R | 20 | | PH | 2-7 | 26-16-11 | D07994P | | 32 | | | | | GD04462 | D.. | 2 | | ALL |
| 028R | 24 | | PP | 34-0 | 26-16-11 | D06944P | | 1 | | | | | D07994P | 33 | | | 050-099, 150-155, 162-165, 275-276 |
| 028R | 24 | | PP | 34-10 | 26-16-11 | D06944P | | 1 | | | | | D07994P | 33 | | | 156-157, 166-199, 277-299 |
| 029R | 20 | | PH | 6-0 | 26-16-11 | D06944P | | 5 | | | | | GD00106 | D.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 029R | 20 | | PH | 7-7 | 26-16-11 | D06944P | | 5 | | | | | GD00106 | D.. | 2 | | 156-157, 166-199, 277-299 |
| 030R | 24 | | PP | 34-0 | 26-16-11 | D06944P | | 11 | | | | | D07994P | 36 | | | 050-099, 150-155, 162-165, 275-276 |
| 030R | 24 | | PP | 34-10 | 26-16-11 | D06944P | | 11 | | | | | D07994P | 36 | | | 156-157, 166-199, 277-299 |
| 031R | 24 | | PP | 34-0 | 26-16-11 | D06944P | | 9 | | | | | D07994P | 35 | | | 050-099, 150-155, 162-165, 275-276 |
| 031R | 24 | | PP | 34-10 | 26-16-11 | D06944P | | 9 | | | | | D07994P | 35 | | | 156-157, 166-199, 277-299 |
| 032R | 20 | | PH | 6-0 | 26-16-11 | D06944P | | 3 | | | | | GD00106 | D.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 032R | 20 | | PH | 7-7 | 26-16-11 | D06944P | | 3 | | | | | GD00106 | D.. | 2 | | 156-157, 166-199, 277-299 |
| 033R | 22 | | PH | 16-3 | 26-16-11 | D00866 | | 12 | | | | | D07994P | 39 | | | ALL |
| 034R | 24 | | PP | 138-0 | 26-16-11 | D06946P | | 2 | | | | | D07994P | 34 | | | 050-099 |
| 034R | 24 | | PP | 160-0 | 26-16-11 | D06946P | | 2 | | | | | D07994P | 34 | | | 150-155, 162-165, 275-276 |
| 034R | 24 | | PP | 155-0 | 26-16-11 | D06946P | | 2 | | | | | D07994P | 34 | | | 156-157, 166-199, 277-299 |
| 035R | 20 | | PH | 5-0 | 26-16-11 | D06946P | | 6 | | | | | GD00108 | D.. | 2 | | 050-099 |
| 035R | 20 | | PH | 6-0 | 26-16-11 | D06946P | | 6 | | | | | GD00108 | D.. | 2 | | 150-155, 162-165, 275-276 |
| 035R | 20 | | PH | 3-1 | 26-16-11 | D06946P | | 6 | | | | | GD00108 | D.. | 2 | | 156-157, 166-199, 277-299 |
| 036R | 24 | | PP | 138-0 | 26-16-11 | D06946P | | 12 | | | | | D07994P | 38 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 10

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | |
| 036R | 24 | | PP | | 160-0 | 26-16-11 | D06946P | 12 | | | D07994P | 38 | | | 150-155, 162-165, 275-276 |
| 036R | 24 | | PP | | 155-0 | 26-16-11 | D06946P | 12 | | | D07994P | 38 | | | 156-157, 166-199, 277-299 |
| 037R | 24 | | PP | | 138-0 | 26-16-11 | D06946P | 10 | | | D07994P | 37 | | | 050-099 |
| 037R | 24 | | PP | | 160-0 | 26-16-11 | D06946P | 10 | | | D07994P | 37 | | | 150-155, 162-165, 275-276 |
| 037R | 24 | | PP | | 155-0 | 26-16-11 | D06946P | 10 | | | D07994P | 37 | | | 156-157, 166-199, 277-299 |
| 038R | 20 | | PH | | 6-0 | 26-16-11 | D06946P | 4 | | | GD00108 | D.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 038R | 20 | | PH | | 3-1 | 26-16-11 | D06946P | 4 | | | GD00108 | D.. | 2 | | 156-157, 166-199, 277-299 |
| 039R | 20 | | PH | | 6-0 | 26-16-11 | D06946P | 8 | | | GD00108 | S.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 039R | 20 | | PH | | 3-1 | 26-16-11 | D06946P | 8 | | | GD00108 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 041R | 22 | | PH | | 15-6 | 26-11-21 | D07994P | 1 | | | D04952P | 11 | | | 050-099 |
| 041R | 22 | | PH | | 15-4 | 26-11-21 | D07994P | 1 | | | D04952P | 11 | | | 150-199, 275-299 |
| 042R | 20 | | PH | | 2-7 | 26-11-21 | D07994P | 2 | | | GD00706 | D.. | 2 | | ALL |
| 044R | 22 | | PH | | 15-6 | 26-11-21 | D07994P | 4 | | | D04952P | 14 | | | 050-099 |
| 044R | 22 | | PH | | 15-4 | 26-11-21 | D07994P | 4 | | | D04952P | 14 | | | 150-199, 275-299 |
| 045R | 22 | | PH | | 17-2 | 26-11-21 | D07994P | 5 | | | D10106 | 5 | | | ALL |
| 046R | 22 | | PH | | 60-7 | 26-11-21 | D07994P | 6 | | | D05522J | 1 | | | 050-099 |
| 046R | 22 | | PH | | 71-1 | 26-11-21 | D07994P | 6 | | | D05522J | 1 | | | 150-199, 275-299 |
| 047R | 22 | | PH | | 60-7 | 26-11-21 | D07994P | 8 | | | D05522J | 2 | | | 050-099 |
| 047R | 22 | | PH | | 71-1 | 26-11-21 | D07994P | 8 | | | D05522J | 2 | | | 150-199, 275-299 |
| 048R | 22 | | PH | | 60-7 | 26-11-21 | D07994P | 7 | | | D05522J | 3 | | | 050-099 |
| 048R | 22 | | PH | | 71-1 | 26-11-21 | D07994P | 7 | | | D05522J | 3 | | | 150-199, 275-299 |
| 049R | 20 | | PH | | 2-7 | 26-11-21 | D07994P | 9 | | | GD00706 | D.. | 2 | | ALL |
| 050R | 22 | | PH | | 17-2 | 26-11-21 | D07994P | 10 | | | D10106 | 6 | | | ALL |
| 051R | 22 | | PH | | 15-6 | 26-11-22 | D07994P | 11 | | | D04952P | 16 | | | 050-099 |
| 051R | 22 | | PH | | 15-4 | 26-11-22 | D07994P | 11 | | | D04952P | 16 | | | 150-199, 275-299 |
| 052R | 20 | | PH | | 2-7 | 26-11-22 | D07994P | 12 | | | GD00706 | D.. | 2 | | ALL |
| 054R | 22 | | PH | | 16-3 | 26-11-22 | D07994P | 14 | | | D10102 | 1 | | | 050-099 |
| 054R | 22 | | PH | | 16-2 | 26-11-22 | D07994P | 14 | | | D10102 | 1 | | | 150-199, 275-299 |
| 055R | 22 | | PH | | 17-2 | 26-11-22 | D07994P | 15 | | | D10106 | 4 | | | ALL |
| 056R | 22 | | PH | | 60-7 | 26-11-22 | D07994P | 17 | | | D05522J | 4 | | | 050-099 |
| 056R | 22 | | PH | | 71-1 | 26-11-22 | D07994P | 17 | | | D05522J | 4 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|---|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | | | |
| 057R | 22 | | PH | 60-7 | 26-11-22 | D07994P | | 18 | | | | | D05522J | 5 | | | 050-099 |
| 057R | 22 | | PH | 71-1 | 26-11-22 | D07994P | | 18 | | | | | D05522J | 5 | | | 150-199, 275-299 |
| 058R | 22 | | PH | 60-7 | 26-11-22 | D07994P | | 16 | | | | | D05522J | 6 | | | 050-099 |
| 058R | 22 | | PH | 71-1 | 26-11-22 | D07994P | | 16 | | | | | D05522J | 6 | | | 150-199, 275-299 |
| 059R | 20 | | PH | 2-7 | 26-11-22 | D07994P | | 19 | | | | | GD00706 | D.. | 2 | | ALL |
| 061R | 22 | | PH | 15-6 | 26-15-11 | D07994P | | 21 | | | | | D04952P | 21 | | | 050-099 |
| 061R | 22 | | PH | 15-4 | 26-15-11 | D07994P | | 21 | | | | | D04952P | 21 | | | 150-199, 275-299 |
| 062R | 20 | | PH | 2-7 | 26-15-11 | D07994P | | 22 | | | | | GD00706 | D.. | 2 | | ALL |
| 064R | 22 | | PH | 15-6 | 26-15-11 | D07994P | | 24 | | | | | D04952P | 32 | | | 050-099 |
| 064R | 22 | | PH | 15-4 | 26-15-11 | D07994P | | 24 | | | | | D04952P | 32 | | | 150-199, 275-299 |
| 066R | 22 | | PH | 115-6 | 26-15-11 | D07994P | | 27 | | | | | D06110P | 1 | | | 050-099 |
| 066R | 22 | | PH | 136-3 | 26-15-11 | D07994P | | 27 | | | | | D06110P | 1 | | | 150-199, 275-299 |
| 067R | 22 | | PH | 115-6 | 26-15-11 | D07994P | | 28 | | | | | D06110P | 2 | | | 050-099 |
| 067R | 22 | | PH | 136-3 | 26-15-11 | D07994P | | 28 | | | | | D06110P | 2 | | | 150-199, 275-299 |
| 068R | 22 | | PH | 115-6 | 26-15-11 | D07994P | | 26 | | | | | D06110P | 3 | | | 050-099 |
| 068R | 22 | | PH | 136-3 | 26-15-11 | D07994P | | 26 | | | | | D06110P | 3 | | | 150-199, 275-299 |
| 069R | 20 | | PH | 2-7 | 26-15-11 | D07994P | | 29 | | | | | GD04462 | D.. | 2 | | ALL |
| 070R | 22 | | PH | 19-1 | 26-15-12 | D07994P | | 20 | | | | | D04948P | 21 | | | 050-099 |
| 070R | 22 | | PH | 19-0 | 26-15-12 | D07994P | | 20 | | | | | D04948P | 21 | | | 150-199, 275-299 |
| 072R | 24 | | PP | 17-2 | 26-16-11 | D07994P | | 43 | | | | | D10106 | 7 | | | ALL |
| 073 | 22 | | PA | 30-11 | 31-31-22 | D06594J | | 9 | | | | | SP02772 | 9 | | | 050-099 |
| 073 | 22 | | PA | 31-0 | 31-31-22 | D06594J | | 9 | | | | | SP02772 | 9 | | | 150-199, 275-299 |
| 074 | 22 | | PA | 30-11 | 31-31-22 | D06594J | | 10 | | | | | SP00377 | 9 | | | 050-099 |
| 074 | 22 | | PA | 31-0 | 31-31-22 | D06594J | | 10 | | | | | SP00377 | 9 | | | 150-199, 275-299 |
| 075 | 22 | | PA | 30-11 | 31-31-22 | D06594J | | 11 | | | | | SP03346 | 9 | | | 050-099 |
| 075 | 22 | | PA | 31-0 | 31-31-22 | D06594J | | 11 | | | | | SP03346 | 9 | | | 150-199, 275-299 |
| 076R | 20 | | PH | 18-9 | 26-23-12 | D00866 | | 17 | | | | | D04952P | 26 | | | 050-099 |
| 076R | 20 | | PH | 18-6 | 26-23-12 | D00866 | | 17 | | | | | D04952P | 26 | | | 150-199, 275-299 |
| 078R | 20 | | PH | 43-8 | 26-21-11 | D04952P | | 3 | | | | | SM00083 | 9 | | | 050-099 |
| 078R | 20 | | PH | 54-4 | 26-21-11 | D04952P | | 3 | | | | | SM00083 | 9 | | | 150-199, 275-299 |
| 079R | 20 | | PH | 43-8 | 26-21-11 | D04952P | | 4 | | | | | SM00012 | 9 | | | 050-099 |
| 079R | 20 | | PH | 54-4 | 26-21-11 | D04952P | | 4 | | | | | SM00012 | 9 | | | 150-199, 275-299 |
| 080R | 20 | | PH | 18-9 | 26-23-12 | D00866 | | 16 | | | | | D04952P | 5 | | | 050-099 |
| 080R | 20 | | PH | 18-6 | 26-23-12 | D00866 | | 16 | | | | | D04952P | 5 | | | 150-199, 275-299 |
| 081R | 20 | | PH | 18-9 | 26-23-12 | D00866 | | 20 | | | | | D04952P | 6 | | | 050-099 |
| 081R | 20 | | PH | 18-6 | 26-23-12 | D00866 | | 20 | | | | | D04952P | 6 | | | 150-199, 275-299 |
| 082R | 20 | | PH | 43-8 | 26-22-21 | D04952P | | 2 | | | | | SM00002 | 9 | | | 050-099 |
| 082R | 20 | | PH | 54-4 | 26-22-21 | D04952P | | 2 | | | | | SM00002 | 9 | | | 150-199, 275-299 |
| 083R | 20 | | PH | 52-11 | 26-21-11 | SP02298 | | | 9 | | | | SM00083 | 9 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 12

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | | | |
| 083R | 20 | | PH | | 63-2 | 26-21-11 | SP02298 | | | | 9 | | | SM00083 | | 9 | 150-199, 275-299 |
| 084R | 20 | | PH | | 50-11 | 26-21-11 | D00862 | | | | 8 | | | SM00012 | | 9 | 050-099 |
| 084R | 20 | | PH | | 61-8 | 26-21-11 | D00862 | | | | 8 | | | SM00012 | | 9 | 150-199, 275-299 |
| 085R | 20 | | PH | | 10-8 | 26-21-11 | D06888P | | | | 9 | | | SM00083 | | 9 | 050-099 |
| 085R | 20 | | PH | | 7-0 | 26-21-11 | D06888P | | | | 9 | | | SM00083 | | 9 | 150-154 |
| 085R | 20 | | PH | | 6-7 | 26-21-11 | D06888P | | | | 9 | | | SM00083 | | 9 | 155-199, 275-299 |
| 088R | 20 | | PH | | 10-8 | 26-21-11 | D06888P | | | | 12 | | | SM00012 | | 9 | 050-099 |
| 088R | 20 | | PH | | 7-0 | 26-21-11 | D06888P | | | | 12 | | | SM00012 | | 9 | 150-154 |
| 088R | 20 | | PH | | 6-7 | 26-21-11 | D06888P | | | | 12 | | | SM00012 | | 9 | 155-199, 275-299 |
| 091R | 20 | | PH | | 59-3 | 26-21-11 | D06888P | | | | 6 | | | SM00091 | | 9 | 050-099 |
| 091R | 20 | | PH | | 66-0 | 26-21-11 | D06888P | | | | 6 | | | SM00091 | | 9 | 150-154 |
| 091R | 20 | | PH | | 65-5 | 26-21-11 | D06888P | | | | 6 | | | SM00091 | | 9 | 155-199, 275-299 |
| 093R | 20 | | PH | | 45-0 | 26-23-12 | D06882P | | | | 12 | | | D04948P | 26 | | 050-099 |
| 093R | 20 | | PH | | 48-0 | 26-23-12 | D06896P | | | | 9 | | | D04948P | 36 | | 150-154 |
| 093R | 20 | | PH | | 47-4 | 26-23-12 | D06896P | | | | 9 | | | D04948P | 26 | | 155-199, 275-299 |
| 096R | 20 | | PH | | 45-0 | 26-23-12 | D06882P | | | | 15 | | | D04948P | 35 | | 050-099 |
| 096R | 20 | | PH | | 48-0 | 26-23-12 | D06896P | | | | 12 | | | D04948P | 37 | | 150-154 |
| 096R | 20 | | PH | | 47-4 | 26-23-12 | D06896P | | | | 12 | | | D04948P | 50 | | 155-199 |
| 096R | 20 | | PH | | 47-4 | 26-23-12 | D06896P | | | | 12 | | | D04948P | 35 | | 275-299 |
| 099 | 18 | | PA | | 18-10 | 78-34-21 | D04952P | | | | 40 | DL | | D00862 | 12 | DK | 050-099 |
| 099 | 18 | | PA | | 18-8 | 78-34-21 | D04952P | | | | 40 | DL | | D00862 | 12 | DK | 150-199, 275-299 |
| 099R | 20 | | PH | | 10-0 | 26-23-12 | D06882P | | | | 8 | | | SM00099 | | 9 | 050-099 |
| 099R | 20 | | PH | | 12-0 | 26-23-12 | D06896P | | | | 6 | | | SM00099 | | 9 | 150-154 |
| 099R | 20 | | PH | | 9-2 | 26-23-12 | D06896P | | | | 6 | | | SM00099 | | 9 | 155-199, 275-299 |
| 102 | 22 | | PA | | 20-5 | 31-31-26 | D04852P | | | | 1 | | | TB0255X | B001 | BJ | 050-099 |
| 102 | 22 | | PA | | 20-10 | 31-31-26 | D04852P | | | | 1 | | | TB0255X | B001 | BJ | 150-199, 275-299 |
| 104R | 22 | | PH | | 7-11 | 26-15-12 | SM00001 | | | | 9 | | | D04948P | 5 | | ALL |
| 105R | 22 | | PH | | 7-2 | 26-15-12 | D03792 | | | | C | | | SM00001 | | 9 | ALL |
| 106R | 22 | | PH | | 7-2 | 26-15-12 | D03792 | | | | F | | | SM00001 | | 9 | ALL |
| 107R | 22 | | PH | | 14-0 | 26-15-12 | D03792 | | | | A | | | D04948P | 6 | | ALL |
| 109 | 24 | | PK | | 104-9 | 31-31-22 | D05054J | | | | 10 | | | D04948P | 48 | | 050-099 |
| 109 | 24 | | PK | | 125-4 | 31-31-22 | D05054J | | | | 10 | | | D04948P | 35 | | 150-199 |
| 109 | 24 | | PK | | 125-4 | 31-31-22 | D05054J | | | | 10 | | | D04948P | 48 | | 275-299 |
| 109R | 20 | | PH | | 3-5 | 26-15-12 | GD00674 | | | | S.. | 2 | | D04950J | 14 | | ALL |
| 110 | 24 | | PK | | 104-9 | 31-31-22 | D05054J | | | | 12 | | | D04948P | 45 | | 050-099 |
| 110 | 24 | | PK | | 125-4 | 31-31-22 | D05054J | | | | 12 | | | D04948P | 45 | | 150-199, 275-299 |
| 110R | 20 | | PH | | 3-5 | 26-15-12 | GD00674 | | | | D.. | 2 | | D04950J | 12 | | ALL |
| 111R | 22 | | PH | | 2-3 | 26-15-12 | SM00111 | | | | 9 | | | D00846 | 20 | | ALL |
| 112R | 22 | | PH | | 9-8 | 26-15-12 | SM00001 | | | | 9 | | | D04950J | 8 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | | | |
| 113R | 22 | | PH | 29-0 | 26-22-21 | SM00111 | | | | 9 | | | | D04950J | 7 | | 050-099 |
| 113R | 22 | | PH | 28-11 | 26-22-21 | SM00111 | | | | 9 | | | | D04950J | 7 | | 150-199, 275-299 |
| 115R | 22 | | PH | 17-1 | 26-15-12 | SM00111 | | | | 9 | | | | D04952P | 35 | | 050-099 |
| 115R | 22 | | PH | 16-10 | 26-15-12 | SM00111 | | | | 9 | | | | D04952P | 35 | | 150-199, 275-299 |
| 117 | 20 | | PA | 35-0 | 26-16-21 | D04952P | | | | 37 | | | | D05214P | 7 | | 050-099 |
| 117 | 20 | | PA | 35-4 | 26-16-21 | D04952P | | | | 37 | | | | D05214P | 7 | | 150-199, 275-299 |
| 118 | 20 | | PA | 35-0 | 26-16-21 | D04952P | | | | 38 | | | | D05214P | 8 | | 050-099 |
| 118 | 20 | | PA | 35-4 | 26-16-21 | D04952P | | | | 38 | | | | D05214P | 8 | | 150-199, 275-299 |
| 119 | 20 | | PA | 6-0 | 26-16-21 | D05214P | | | | 9 | | | | GD04324 | D.. 2 | | 050-099 |
| 119 | 20 | | PA | 6-4 | 26-16-21 | D05214P | | | | 9 | | | | GD04324 | D.. 2 | | 150-199, 275-299 |
| 120 | 24 | | PK | 28-0 | 26-16-21 | D05214P | | | | 4 | | | | D04948P | 20 | | 050-099 |
| 120 | 24 | | PK | 28-4 | 26-16-21 | D05214P | | | | 4 | | | | D04948P | 20 | | 150-199, 275-299 |
| 121 | 20 | | PA | 32-0 | 26-16-21 | D01136 | | | | 1 | | | | D05214P | 1 | | 050-099 |
| 121 | 20 | | PA | 32-2 | 26-16-21 | D01136 | | | | 1 | | | | D05214P | 1 | | 150-199, 275-299 |
| 122 | 20 | | PA | 3-4 | 26-16-21 | D01136 | | | | 2 | | | | GD00106 | A.. 2 | | ALL |
| 123 | 20 | | PA | 32-0 | 26-16-21 | D06948P | | | | 1 | | | | D05214P | 2 | | 050-099 |
| 123 | 20 | | PA | 33-0 | 26-16-21 | D06948P | | | | 1 | | | | D05214P | 2 | | 150-155, 162-165 |
| 123 | 20 | | PA | 31-7 | 26-16-21 | D06948P | | | | 1 | | | | D05214P | 2 | | 156-157, 166-199, 277-299 |
| 123 | 20 | | PA | 38-0 | 26-16-21 | D06948P | | | | 1 | | | | D05214P | 2 | | 275-276 |
| 124 | 20 | | PA | 4-0 | 26-16-21 | D06948P | | | | 2 | | | | GD00106 | A.. 2 | | 050-099, 150-155, 162-165, 275-276 |
| 124 | 20 | | PA | 9-4 | 26-16-21 | D06948P | | | | 2 | | | | GD00106 | A.. 2 | | 156-157, 166-199, 277-299 |
| 125 | 20 | | PA | 13-5 | 26-16-21 | D01444 | | | | 3 | | | | SM00125 | 9 | | ALL |
| 126 | 20 | | PA | 4-8 | 26-16-21 | D01444 | | | | 2 | | | | GD00106 | D.. 2 | | ALL |
| 127 | 20 | | PA | 18-0 | 26-16-21 | D05214P | | | | 3 | | | | SM00125 | 9 | | 050-099 |
| 127 | 20 | | PA | 18-6 | 26-16-21 | D05214P | | | | 3 | | | | SM00125 | 9 | | 150-199, 275-299 |
| 128 | 20 | | PA | 12-7 | 26-16-21 | D04948P | | | | 23 | | | | SM00125 | 9 | | ALL |
| 129 | 20 | | PA | 4-8 | 26-16-21 | D01444 | | | | 4 | | | | GD00106 | S.. 2 | | ALL |
| 130 | 24 | | PK | 28-0 | 26-16-21 | D05214P | | | | 14 | | | | D04948P | 22 | | 050-099 |
| 130 | 24 | | PK | 28-4 | 26-16-21 | D05214P | | | | 14 | | | | D04948P | 22 | | 150-199, 275-299 |
| 131 | 20 | | PA | 119-0 | 26-16-21 | D01140 | | | | 1 | | | | D05214P | 11 | | 050-099 |
| 131 | 20 | | PA | 139-5 | 26-16-21 | D01140 | | | | 1 | | | | D05214P | 11 | | 150-156, 162-166, 275-276 |
| 131 | 20 | | PA | 138-6 | 26-16-21 | D01140 | | | | 1 | | | | D05214P | 11 | | 157, 167-199, 277-299 |
| 132 | 20 | | PA | 3-3 | 26-16-21 | D01140 | | | | 2 | | | | GD00108 | A.. 2 | | 050-099 |
| 132 | 20 | | PA | 3-6 | 26-16-21 | D01140 | | | | 2 | | | | GD00108 | A.. 2 | | 150-156, 162-166, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 14

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | |
| 132 | 20 | PA | | 2-7 | 26-16-21 | D01140 | | 2 | | GD00108 | A.. | 2 | | 157, 167-199, 277-299 | |
| 133 | 20 | PA | | 117-0 | 26-16-21 | D06950P | | 1 | | D05214P | 12 | | | 050-099 | |
| 133 | 20 | PA | | 140-0 | 26-16-21 | D06950P | | 1 | | D05214P | 12 | | | 150-155, 162-165, 275-276 | |
| 133 | 20 | PA | | 138-11 | 26-16-21 | D06950P | | 1 | | D05214P | 12 | | | 156-157, 166-199, 277-299 | |
| 134 | 20 | PA | | 4-0 | 26-16-21 | D06950P | | 2 | | GD00108 | A.. | 2 | | 050-099, 150-155, 162-165, 275-276 | |
| 134 | 20 | PA | | 3-0 | 26-16-21 | D06950P | | 2 | | GD00108 | A.. | 2 | | 156-157, 166-199, 277-299 | |
| 135 | 20 | PA | | 101-5 | 26-16-21 | D01446 | | 3 | | SM00135 | | 9 | | 050-099 | |
| 135 | 20 | PA | | 122-6 | 26-16-21 | D01446 | | 3 | | SM00135 | | 9 | | 150-156, 162-166, 275-276 | |
| 135 | 20 | PA | | 122-4 | 26-16-21 | D01446 | | 3 | | SM00135 | | 9 | | 157, 167-199, 277-299 | |
| 136 | 20 | PA | | 3-6 | 26-16-21 | D01446 | | 2 | | GD00108 | D.. | 2 | | 050-099 | |
| 136 | 20 | PA | | 3-10 | 26-16-21 | D01446 | | 2 | | GD00108 | D.. | 2 | | 150-156, 162-166, 275-276 | |
| 136 | 20 | PA | | 3-8 | 26-16-21 | D01446 | | 2 | | GD00108 | D.. | 2 | | 157, 167-199, 277-299 | |
| 137 | 20 | PA | | 7-2 | 31-31-22 | SP02774 | | 9 | | GD03816 | D.. | E | | 050-099 | |
| 137 | 20 | PA | | 7-8 | 31-31-22 | SP02774 | | 9 | | GD03816 | D.. | E | *1 | 150-199 | |
| 137 | 20 | PA | | 7-8 | 31-31-22 | SP02774 | | 9 | | GD03816 | D.. | E | | 275-299 | |
| 138 | 20 | PA | | 7-2 | 31-31-22 | SP03344 | | 9 | | GD03816 | D.. | E | | 050-099 | |
| 138 | 20 | PA | | 7-8 | 31-31-22 | SP03344 | | 9 | | GD03816 | D.. | E | *1 | 150-199 | |
| 138 | 20 | PA | | 7-8 | 31-31-22 | SP03344 | | 9 | | GD03816 | D.. | E | | 275-299 | |
| 139 | 20 | PA | | 3-6 | 26-16-21 | D01446 | | 4 | | GD00108 | S.. | 2 | | 050-099 | |
| 139 | 20 | PA | | 3-10 | 26-16-21 | D01446 | | 4 | | GD00108 | S.. | 2 | | 150-156, 162-166, 275-276 | |
| 139 | 20 | PA | | 3-8 | 26-16-21 | D01446 | | 4 | | GD00108 | S.. | 2 | | 157, 167-199, 277-299 | |
| 143 | 22 | PA | | 89-2 | SPARE | D04652J | | 9 | | D04852P | | 2 | | 150-199, 275-299 | |
| 144R | 20 | PH | | 61-7 | 26-22-21 | D00846 | | 8 | | SM00004 | | 9 | | 275-299 | |
| 145R | 20 | PH | | 54-4 | 26-22-21 | D04952P | | 43 | | SM00004 | | 9 | | 275-299 | |
| 148R | 22 | PH | | 19-1 | 26-17-11 | D07994P | | 48 | | D04948P | | 28 | | 050-099 | |
| 148R | 22 | PH | | 19-0 | 26-17-11 | D07994P | | 48 | | D04948P | | 28 | | 150-199, 275-299 | |
| 149R | 22 | PH | | 19-1 | 26-17-11 | D07994P | | 49 | | D04948P | | 29 | | 050-099 | |
| 149R | 22 | PH | | 19-0 | 26-17-11 | D07994P | | 49 | | D04948P | | 29 | | 150-199, 275-299 | |
| 150 | 20 | PQ | A | 16-6 | 49-61-11 | D04950J | | 6 | | D04948P | | 8 | | ALL | |
| 150Z | | | A | 0-0 | 49-61-11 | D04950J | | DED | | D04948P | DED | | | ALL | |
| 152 | 24 | PK | | 104-9 | 49-15-11 | D05054J | | 2 | | D04948P | | 3 | | 050-099 | |
| 152 | 24 | PK | | 125-4 | 49-15-11 | D05054J | | 2 | | D04948P | | 3 | | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 15

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | | | |
| 154 | 16 | PA | | 111-10 | 49-61-11 | D05054J | | 4 | | | | | D04952P | 27 | FL | | 050-099 |
| 154 | 16 | PA | | 132-3 | 49-61-11 | D05054J | | 4 | | | | | D04952P | 27 | FL | | 150-199, 275-299 |
| 155 | 20 | PA | | 3-4 | 26-16-21 | D01136 | | 3 | | | | | GD00106 | S.. | 2 | | ALL |
| 156 | 20 | PA | | 4-0 | 26-16-21 | D06948P | | 3 | | | | | GD00106 | S.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 156 | 20 | PA | | 9-4 | 26-16-21 | D06948P | | 3 | | | | | GD00106 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 157 | 20 | PA | | 3-3 | 26-16-21 | D01140 | | 3 | | | | | GD00108 | S.. | 2 | | 050-099 |
| 157 | 20 | PA | | 3-6 | 26-16-21 | D01140 | | 3 | | | | | GD00108 | S.. | 2 | | 150-156, 162-166, 275-276 |
| 157 | 20 | PA | | 2-7 | 26-16-21 | D01140 | | 3 | | | | | GD00108 | S.. | 2 | | 157, 167-199, 277-299 |
| 158 | 20 | PA | | 4-0 | 26-16-21 | D06950P | | 3 | | | | | GD00108 | S.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 158 | 20 | PA | | 3-0 | 26-16-21 | D06950P | | 3 | | | | | GD00108 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 167 | 24 | PK | | 111-10 | 24-31-41 | D05054J | | 8 | | | | | D04952P | 41 | | | 050-099 |
| 167 | 24 | PK | | 132-3 | 24-31-41 | D05054J | | 8 | | | | | D04952P | 41 | | | 150-199, 275-299 |
| 170R | 18 | PH | | 112-9 | 26-18-31 | D01510 | | = 1 | | | | | D04952P | 42 | DL | | 050-099 |
| 170R | 18 | PH | | 122-6 | 26-18-31 | D01510 | | = 1 | | | | | D04952P | 42 | DL | | 150-199, 275-299 |
| 171R | 18 | PH | | 50-4 | 26-18-31 | D01512 | | = 1 | | | | | D06110P | 8 | DK | | 050-099 |
| 171R | 18 | PH | | 61-0 | 26-18-31 | D01512 | | = 1 | | | | | D06110P | 8 | DK | | 150-199, 275-299 |
| 172 | 22 | PA | | 104-9 | 49-61-11 | D05054J | | 3 | | | | | D04948P | 16 | | | 050-099 |
| 172 | 22 | PA | | 125-4 | 49-61-11 | D05054J | | 3 | | | | | D04948P | 16 | | | 150-199, 275-299 |
| 173R | 22 | PH | | 22-4 | 26-15-12 | D00846 | | 39 | | | | | D04948P | 15 | | | ALL |
| 174 | 22 | PA | | 15-3 | 49-61-11 | D04952P | | 34 | | | | | D04948P | 14 | | | 050-099 |
| 174 | 22 | PA | | 15-1 | 49-61-11 | D04952P | | 34 | | | | | D04948P | 14 | | | 150-199, 275-299 |
| 176 | 20 | PA | | 2-9 | 21-25-11 | GD04456 | | D.. | 2 | | | | D00866 | 10 | | | ALL |
| 177 | 24 | PK | | 18-9 | 21-25-11 | D04952P | | 54 | | | | | D00866 | 13 | | | 050-099 |
| 177 | 24 | PK | | 18-6 | 21-25-11 | D04952P | | 54 | | | | | D00866 | 13 | | | 150-199, 275-299 |
| 178R | 20 | PH | | 2-9 | 26-23-12 | D00866 | | 23 | | | | | GD04456 | D.. | 2 | | ALL |
| 179R | 20 | PH | | 50-9 | 26-23-12 | D00866 | | 15 | | | | | SM00099 | 9 | | | 050-099 |
| 179R | 20 | PH | | 53-10 | 26-23-12 | D00866 | | 15 | | | | | SM00099 | 9 | | | 150-199, 275-299 |
| 180R | 22 | PH | | 18-10 | 26-11-21 | D00862 | | 10 | | | | | D04952P | 12 | | | 050-099 |
| 180R | 22 | PH | | 18-8 | 26-11-21 | D00862 | | 10 | | | | | D04952P | 12 | | | 150-199, 275-299 |
| 181R | 20 | PH | | 2-11 | 26-11-21 | D00862 | | 24 | | | | | GD04456 | S.. | 2 | | ALL |
| 182R | 22 | PH | | 18-10 | 26-11-21 | D00862 | | 2 | | | | | D04952P | 13 | | | 050-099 |
| 182R | 22 | PH | | 18-8 | 26-11-21 | D00862 | | 2 | | | | | D04952P | 13 | | | 150-199, 275-299 |
| 185R | 22 | PH | | 18-10 | 26-11-21 | D00862 | | 25 | | | | | D04952P | 36 | | | 050-099 |
| 185R | 22 | PH | | 18-8 | 26-11-21 | D00862 | | 25 | | | | | D04952P | 36 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 16

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | | |
| 186R | 20 | | PH | | 79-6 | 26-22-21 | D06110P | | | | SM00004 | | | | 9 | 275-299 |
| 187R | 20 | | PH | | 130-9 | 26-22-21 | D06110P | | | | SP02480 | | | | 9 | 275-299 |
| 194 | 18 | | PA | | 18-10 | 78-34-21 | D04952P | | 39 | DL | D00862 | | 3 | DK | | 050-099 |
| 194 | 18 | | PA | | 18-8 | 78-34-21 | D04952P | | 39 | DL | D00862 | | 3 | DK | | 150-199, 275-299 |
| 195R | 20 | | PH | | 18-10 | 26-21-11 | D04952P | | | | D00862 | | | | 9 | 050-099 |
| 195R | 20 | | PH | | 18-8 | 26-21-11 | D04952P | | | | D00862 | | | | 9 | 150-199, 275-299 |
| 196R | 20 | | PH | | 20-4 | 26-21-11 | D04952P | | | | SP02296 | | | | 9 | 050-099 |
| 196R | 20 | | PH | | 20-2 | 26-21-11 | D04952P | | | | SP02296 | | | | 9 | 150-199, 275-299 |
| 197R | 20 | | PH | | 4-11 | 26-21-11 | SP02300 | | | | D00862 | | | | 22 | ALL |
| 198R | 20 | | PH | | 4-11 | 26-21-11 | D00862 | | | | SP02302 | | | | 9 | ALL |
| 199R | 20 | | PH | | 2-2 | 26-21-11 | D10102 | | | | SM00091 | | | | 9 | ALL |
| 201B | 20 | | PR | AB | 16-6 | 32-45-12 | D04948P | | | | D04950J | | | | 15 | 050-099 |
| 201B | 20 | | PR | AB | 16-6 | 32-45-12 | D04950J | | | | D04948P | | | | 43 | 150-199 |
| 201B | 20 | | PR | IA | 16-6 | 32-45-12 | D04948P | | | | D04950J | | | | 15 | 275-299 |
| 201R | 20 | | PR | AB | 0-0 | 32-45-12 | D04948P | | | | D04950J | | | | 16 | 050-099 |
| 201R | 20 | | PR | AB | 0-0 | 32-45-12 | D04950J | | | | D04948P | | | | 42 | 150-199 |
| 201R | 20 | | PR | IA | 0-0 | 32-45-12 | D04948P | | | | D04950J | | | | 16 | 275-299 |
| 201Z | | | | AB | 0-0 | 32-45-12 | D04948P | | | | D04950J | | | | 1 | 050-099 |
| 201Z | | | | AB | 0-0 | 32-45-12 | D04950J | | | | D04948P | | | | 44 | 150-199 |
| 201Z | | | | IA | 0-0 | 32-45-12 | D04948P | | | | D04950J | | | | 1 | 275-299 |
| 202B | 22 | | PR | IB | 19-3 | 31-31-22 | SP03266 | | | | D06594J | | | | 7 | 050-099 |
| 202B | 22 | | PR | AD | 52-1 | 31-31-22 | SP03266 | | | | D06594J | | | | 7 | 150-199 |
| 202B | 22 | | PR | IB | 52-1 | 31-31-22 | D06594J | | | 7 | SP03266 | | | | S | 275-299 |
| 202R | 22 | | PR | IB | 0-0 | 31-31-22 | SP03264 | | | | D06594J | | | | 6 | 050-099 |
| 202R | 22 | | PR | AD | 0-0 | 31-31-22 | SP03264 | | | | D06594J | | | | 6 | 150-199 |
| 202R | 22 | | PR | IB | 0-0 | 31-31-22 | D06594J | | | 6 | SP03264 | | | | S | 275-299 |
| 202Z | | | | IB | 0-0 | 31-31-22 | SP03268 | | | | D06594J | | | | 8 | 050-099 |
| 202Z | | | | AD | 0-0 | 31-31-22 | SP03268 | | | | D06594J | | | | 8 | 150-199 |
| 202Z | | | | IB | 0-0 | 31-31-22 | D06594J | | | | SP03268 | | | | S | 275-299 |
| 203B | 22 | | PR | IC | 68-4 | 31-31-22 | D04652J | | | | D06594J | | | | 2 | 050-099 |
| 203B | 22 | | PR | AE | 78-8 | 31-31-22 | D04652J | | | | D06594J | | | | 2 | 150-199 |
| 203B | 22 | | PR | IC | 78-8 | 31-31-22 | D06594J | | | | D04652J | | | | 11 | 275-299 |
| 203R | 22 | | PR | IC | 0-0 | 31-31-22 | D04652J | | | | D06594J | | | | 1 | 050-099 |
| 203R | 22 | | PR | AE | 0-0 | 31-31-22 | D04652J | | | | D06594J | | | | 1 | 150-199 |
| 203R | 22 | | PR | IC | 0-0 | 31-31-22 | D06594J | | | | D04652J | | | | 10 | 275-299 |
| 203Z | | | | IC | 0-0 | 31-31-22 | D04652J | | | | D06594J | | | | 3 | 050-099 |
| 203Z | | | | AE | 0-0 | 31-31-22 | D04652J | | | | D06594J | | | | 3 | 150-199 |
| 203Z | | | | IC | 0-0 | 31-31-22 | D06594J | | | | D04652J | | | | 8 | 275-299 |
| 301B | 24 | | PM | WO | 111-8 | 49-94-14 | D05054J | | | | D04852P | | | | 22 | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0600
Page 17
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | | | | |
| 301B | 24 | | PM | AC | 132-1 | 49-94-14 | D04852P | | 22 | | | | D05054J | | 6 | | | 150-199 |
| 301B | 24 | | PM | MA | 132-1 | 49-94-14 | D04852P | | 22 | | | | D05054J | | 6 | | | 275-299 |
| 301R | 24 | | PM | WO | 0-0 | 49-94-14 | D05054J | | 5 | | | | D04852P | | 21 | | | 050-099 |
| 301R | 24 | | PM | AC | 0-0 | 49-94-14 | D04852P | | 21 | | | | D05054J | | 5 | | | 150-199 |
| 301R | 24 | | PM | MA | 0-0 | 49-94-14 | D04852P | | 21 | | | | D05054J | | 5 | | | 275-299 |
| 301Y | 24 | | PM | WO | 0-0 | 49-94-14 | D05054J | | 7 | | | | D04852P | | 23 | | | 050-099 |
| 301Y | 24 | | PM | AC | 0-0 | 49-94-14 | D04852P | | 23 | | | | D05054J | | 7 | | | 150-199 |
| 301Y | 24 | | PM | MA | 0-0 | 49-94-14 | D04852P | | 23 | | | | D05054J | | 7 | | | 275-299 |
| 501 | 24 | | PK | | 18-10 | 24-22-21 | D00862 | | 21 | | | | D04952P | | 44 | | | 050-099 |
| 501 | 24 | | PK | | 18-8 | 24-22-21 | D00862 | | 21 | | | | D04952P | | 44 | | | 150-199, 275-299 |
| 505 | 24 | | PK | | 18-10 | 36-11-52 | D00862 | | 35 | | | | D04952P | | 8 | | | 050-099 |
| 505 | 24 | | PK | | 18-8 | 36-11-52 | D00862 | | 35 | | | | D04952P | | 8 | | | 150-199, 275-299 |
| 506 | 22 | | PA | | 64-0 | 29-11-21 | D00862 | | 36 | | | | D05522J | | 10 | | | 050-099 |
| 506 | 22 | | PA | | 74-6 | 29-11-21 | D00862 | | 36 | | | | D05522J | | 10 | | | 150-199, 275-299 |
| 507 | 22 | | PA | | 64-0 | 29-11-21 | D00862 | | 37 | | | | D05522J | | 11 | | | 050-099 |
| 507 | 22 | | PA | | 74-6 | 29-11-21 | D00862 | | 37 | | | | D05522J | | 11 | | | 150-199, 275-299 |
| 509 | 24 | | PK | | 18-10 | 78-34-21 | D00862 | | 39 | | | | D04952P | | 31 | | | 050-099 |
| 509 | 24 | | PK | | 18-8 | 78-34-21 | D00862 | | 39 | | | | D04952P | | 31 | | | 150-199, 275-299 |
| 510 | 24 | | PK | | 18-10 | 24-22-21 | D00862 | | 40 | | | | D04952P | | 45 | | | 050-099 |
| 510 | 24 | | PK | | 18-8 | 24-22-21 | D00862 | | 40 | | | | D04952P | | 45 | | | 150-199, 275-299 |
| 512 | 20 | | PA | | 18-10 | 76-11-11 | D00862 | | 6 | | | | D04952P | | 52 | | | 050-099 |
| 512 | 20 | | PA | | 18-8 | 76-11-11 | D00862 | | 6 | | | | D04952P | | 52 | | | 150-199, 275-299 |
| 513 | 20 | | PA | | 18-10 | 76-11-11 | D00862 | | 7 | | | | D04952P | | 53 | | | 050-099 |
| 513 | 20 | | PA | | 18-8 | 76-11-11 | D00862 | | 7 | | | | D04952P | | 53 | | | 150-199, 275-299 |
| 515 | 20 | | PA | | 2-11 | 31-51-33 | D00862 | | 15 | | | | GD04456 | | D.. 2 | | | ALL |
| 516 | 18 | | PA | | 2-11 | 78-34-21 | D00862 | | 11 | DK | | | GD04456 | | D.. 2 | | | ALL |
| 517 | 20 | | PA | | 2-11 | 36-11-52 | D00862 | | 17 | | | | GD04456 | | D.. 2 | | | ALL |
| 518 | 22 | | PA | | 18-10 | 29-11-21 | D00862 | | 18 | | | | D04952P | | 46 | | | 050-099 |
| 518 | 22 | | PA | | 18-8 | 29-11-21 | D00862 | | 18 | | | | D04952P | | 46 | | | 150-199, 275-299 |
| 519 | 20 | | PA | | 18-10 | 76-11-11 | D00862 | | 19 | | | | D04952P | | 51 | | | 050-099 |
| 519 | 20 | | PA | | 18-8 | 76-11-11 | D00862 | | 19 | | | | D04952P | | 51 | | | 150-199, 275-299 |
| 520 | 24 | | PK | | 18-10 | 78-34-21 | D00862 | | 20 | | | | D04952P | | 55 | | | 050-099 |
| 520 | 24 | | PK | | 18-8 | 78-34-21 | D00862 | | 20 | | | | D04952P | | 55 | | | 150-199, 275-299 |
| 523 | 24 | | PK | | 18-9 | 24-22-41 | D00846 | | 21 | | | | D04952P | | 25 | | | 050-099 |
| 523 | 24 | | PK | | 18-7 | 24-22-41 | D00846 | | 21 | | | | D04952P | | 25 | | | 150-199, 275-299 |
| 524 | 24 | | PK | | 18-9 | 24-22-41 | D00846 | | 40 | | | | D04952P | | 24 | | | 050-099 |
| 524 | 24 | | PK | | 18-7 | 24-22-41 | D00846 | | 40 | | | | D04952P | | 24 | | | 150-199, 275-299 |
| 525 | 24 | | PK | | 22-4 | 36-11-41 | D00846 | | 35 | | | | D04948P | | 17 | | | ALL |
| 526R | 20 | | PH | | 2-3 | 26-22-21 | D00846 | | 8 | | | | SM00015 | | | 9 | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 18

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|--------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | |
| 527R | 20 | | PH | 2-3 | 26-22-21 | D00846 | | 9 | | SM00014 | | 9 | | 050-099, 150-199 | |
| 527R | 20 | | PH | 18-7 | 26-22-21 | D00846 | | 9 | | D04952P | | 30 | | 275-299 | |
| 528R | 20 | | PH | 2-3 | 26-22-21 | D00846 | | 22 | | SM00014 | | 9 | | 050-099, 150-199 | |
| 529R | 20 | | PH | 2-3 | 26-22-21 | D00846 | | 23 | | SM00015 | | 9 | | 050-099, 150-199 | |
| 534R | 22 | | PH | 18-9 | 26-15-11 | D00846 | | 10 | | D04952P | | 28 | | 050-099 | |
| 534R | 22 | | PH | 18-7 | 26-15-11 | D00846 | | 10 | | D04952P | | 28 | | 150-199, 275-299 | |
| 535 | 20 | | PA | 2-10 | 31-51-33 | D00846 | | 15 | | GD04456 | D.. | 2 | | ALL | |
| 537 | 24 | | PK | 22-4 | 36-11-41 | D00846 | | 17 | | D04948P | | 18 | | ALL | |
| 540R | 22 | | PH | 18-9 | 26-15-11 | D00846 | | 25 | | D04952P | | 29 | | 050-099 | |
| 540R | 22 | | PH | 18-7 | 26-15-11 | D00846 | | 25 | | D04952P | | 29 | | 150-199, 275-299 | |
| 541R | 22 | | PH | 18-9 | 26-15-11 | D00846 | | 2 | | D04952P | | 33 | | 050-099 | |
| 541R | 22 | | PH | 18-7 | 26-15-11 | D00846 | | 2 | | D04952P | | 33 | | 150-199, 275-299 | |
| 542R | 20 | | PH | 2-10 | 26-15-11 | D00846 | | 24 | | GD04456 | S.. | 2 | | ALL | |
| 543 | 22 | | PA | 111-10 | 80-11-11 | D04952P | | 15 | | D05054J | | 9 | | 050-099 | |
| 543 | 22 | | PA | 132-3 | 80-11-11 | D04952P | | 15 | | D05054J | | 9 | | 150-199, 275-299 | |
| 544 | 22 | | PQ | VS | 18-10 | 29-11-21 | D00862 | | 13 | D04952P | | 47 | | 050-099 | |
| 544 | 22 | | PQ | VS | 18-8 | 29-11-21 | D00862 | | 13 | D04952P | | 47 | | 150-199, 275-299 | |
| 544Z | | | | VS | 0-0 | 29-11-21 | D00862 | DED | | D04952P | DED | | | ALL | |
| 545 | 22 | | PQ | VT | 18-10 | 29-11-21 | D00862 | | 28 | D04952P | | 48 | | 050-099 | |
| 545 | 22 | | PQ | VT | 18-8 | 29-11-21 | D00862 | | 28 | D04952P | | 48 | | 150-199, 275-299 | |
| 545Z | | | | VT | 0-0 | 29-11-21 | D00862 | DED | | D04952P | DED | | | ALL | |
| 546 | 22 | | PA | 18-9 | 49-61-11 | D00846 | | 6 | | D04952P | | 17 | | 050-099 | |
| 546 | 22 | | PA | 18-7 | 49-61-11 | D00846 | | 6 | | D04952P | | 17 | | 150-199, 275-299 | |
| 547 | 22 | | PA | 18-9 | 49-61-11 | D00846 | | 7 | | D04952P | | 18 | | 050-099 | |
| 547 | 22 | | PA | 18-7 | 49-61-11 | D00846 | | 7 | | D04952P | | 18 | | 150-199, 275-299 | |
| 548 | 22 | | PA | 22-4 | 49-61-11 | D00846 | | 19 | | D04948P | | 11 | | ALL | |
| 549 | 24 | | PK | 11-0 | 31-51-33 | D00846 | | 4 | | TB0031F | A023 | 2 | | 050-099 | |
| 549 | 24 | | PK | 20-9 | 31-51-33 | D00846 | | 4 | | TB0031F | A023 | 2 | | 150-199 | |
| 549 | 24 | | PK | 11-9 | 31-51-33 | D00846 | | 4 | | TB0031F | A023 | 2 | | 275-299 | |
| 550 | 24 | | PK | 11-1 | 31-51-33 | D00862 | | 4 | | TB0031F | C026 | 2 | | 050-099 | |
| 550 | 24 | | PK | 11-10 | 31-51-33 | D00862 | | 4 | | TB0031F | C026 | 2 | | 150-199, 275-299 | |
| 551 | 22 | | PA | 11-0 | 33-16-18 | D10102 | | 3 | | TB0031H | | 18 | 2 | 050-099 | |
| 551 | 22 | | PA | 11-8 | 33-16-18 | D10102 | | 3 | | TB0031H | | 18 | 2 | 150-199, 275-299 | |
| 552 | 22 | | PA | 11-0 | 33-16-18 | D10102 | | 4 | | TB0031H | | 13 | 2 | 050-099 | |
| 552 | 22 | | PA | 11-8 | 33-16-18 | D10102 | | 4 | | TB0031H | | 13 | 2 | 150-199, 275-299 | |
| 553 | 22 | | PA | 12-0 | 33-16-18 | D00862 | | 1 | | TB0031H | | 16 | 2 | 050-099 | |
| 553 | 22 | | PA | 11-10 | 33-16-18 | D00862 | | 1 | | TB0031H | | 16 | 2 | 150-199, 275-299 | |
| 554 | 22 | | PA | 11-0 | 33-16-18 | D00866 | | 3 | | TB0031H | | 16 | 2 | 050-099 | |
| 554 | 22 | | PA | 11-8 | 33-16-18 | D00866 | | 3 | | TB0031H | | 16 | 2 | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 19

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|---------|-------|-------------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | |
| 555 | 22 | PA | | | 10-11 | 33-16-18 | D00866 | | 4 | | TB0031G | 15 | 2 | | 050-099 |
| 555 | 22 | PA | | | 11-8 | 33-16-18 | D00866 | | 4 | | TB0031G | 15 | 2 | | 150-199, 275-299 |
| 556 | 20 | PA | | | 18-10 | 28-22-21 | D04952P | | 49 | | D00862 | 16 | | | 050-099 |
| 556 | 20 | PA | | | 18-8 | 28-22-21 | D04952P | | 49 | | D00862 | 16 | | | 150-199, 275-299 |
| 557 | 20 | PA | | | 18-10 | 28-22-21 | D04952P | | 50 | | D00862 | 33 | | | 050-099 |
| 557 | 20 | PA | | | 18-8 | 28-22-21 | D04952P | | 50 | | D00862 | 33 | | | 150-199, 275-299 |
| 558 | 24 | PK | | | 18-9 | 21-44-11 | D04952P | | 22 | | D00866 | 8 | | | 050-099 |
| 558 | 24 | PK | | | 18-6 | 21-44-11 | D04952P | | 22 | | D00866 | 8 | | | 150-199, 275-299 |
| 559 | 24 | PK | | | 18-9 | 21-44-11 | D04952P | | 9 | | D00866 | 7 | | | 050-099 |
| 559 | 24 | PK | | | 18-6 | 21-44-11 | D04952P | | 9 | | D00866 | 7 | | | 150-199, 275-299 |
| 560 | 22 | PA | | | 11-0 | 33-16-18 | D00846 | | 1 | | TB0031H | 16 | 2 | | 050-099 |
| 560 | 22 | PA | | | 11-9 | 33-16-18 | D00846 | | 1 | | TB0031H | 16 | 2 | | 150-199, 275-299 |
| 561R | 20 | PH | | | 36-7 | 26-23-12 | D04948P | | 4 | | SM00099 | | 9 | | 050-099 |
| 561R | 20 | PH | | | 39-2 | 26-23-11 | D04948P | | 4 | | SM00099 | | 9 | | 150-154 |
| 561R | 20 | PH | | | 39-2 | 26-23-12 | D04948P | | 4 | | SM00099 | | 9 | | 155-199, 275-299 |
| 562 | 24 | PK | | | 10-11 | 31-51-33 | D00866 | | 21 | | TB0031Y | A003 | BJ | | 050-099 |
| 562 | 24 | PK | | | 11-8 | 31-51-33 | D00866 | | 21 | | TB0031Y | A003 | BJ | | 150-199, 275-299 |
| 563R | 20 | PH | | | 20-8 | 26-21-11 | D04948P | | 13 | | SM00091 | | 9 | | 050-099 |
| 563R | 20 | PH | | | 20-7 | 26-21-11 | D04948P | | 13 | | SM00091 | | 9 | | 150-199, 275-299 |
| 564 | 20 | PQ | WN | | 12-4 | 28-25-21 | D00846 | | 32 | | SP02294 | | 9 | | 050-099 |
| 564 | 20 | PQ | WN | | 12-3 | 28-25-21 | D00846 | | 32 | | SP02294 | | 9 | | 150-199, 275-299 |
| 564Z | | | WN | | 0-0 | 28-25-21 | D00846 | DED | | | SP02294 | DED | | | ALL |
| 565 | 22 | PA | | | 18-9 | 28-25-21 | D00846 | | 16 | | D04952P | 23 | | | 050-099 |
| 565 | 20 | PA | | | 18-7 | 28-25-21 | D00846 | | 16 | | D04952P | 23 | | | 150-199, 275-299 |
| 566 | 22 | PA | | | 22-4 | 28-25-21 | D00846 | | 33 | | D04948P | 7 | | | 050-099 |
| 566 | 20 | PA | | | 22-4 | 28-25-21 | D00846 | | 33 | | D04948P | 7 | | | 150-199, 275-299 |
| 593R | 20 | PH | | | 46-0 | 26-23-12 | D06884P | | 8 | | D04948P | 36 | | | 050-099 |
| 593R | 20 | PH | | | 44-6 | 26-23-12 | D06898P | | 12 | | D04948P | 36 | | | 155-199, 275-299 |
| 596R | 20 | PH | | | 46-0 | 26-23-12 | D06884P | | 11 | | D04948P | 37 | | | 050-099 |
| 596R | 20 | PH | | | 44-6 | 26-23-12 | D06898P | | 15 | | D04948P | 37 | | | 155-199, 275-299 |
| 599R | 20 | PH | | | 10-6 | 26-23-12 | D06884P | | 5 | | SM00099 | | 9 | | 050-099 |
| 599R | 20 | PH | | | 9-4 | 26-23-12 | D06898P | | 8 | | SM00099 | | 9 | | 155-199, 275-299 |
| 625R | 20 | PH | | | 22-4 | 26-23-12 | D04948P | | 25 | | D00866 | 22 | | | 050-099 |
| 625R | 20 | PH | | | 22-3 | 26-23-12 | D00866 | | 22 | | D04948P | 25 | | | 150-199, 275-299 |
| 626R | 20 | PH | | | 22-4 | 26-23-12 | D04948P | | 34 | | D00866 | 5 | | | 050-099 |
| 626R | 20 | PH | | | 22-3 | 26-23-12 | D00866 | | 5 | | D04948P | 34 | | | 150-199, 275-299 |
| 627R | 22 | PH | | | 15-1 | 26-17-11 | D04948P | | 27 | | D04852P | 7 | | | 050-099 |
| 627R | 22 | PH | | | 14-11 | 26-17-11 | D04948P | | 27 | | D04852P | 7 | | | 150-199, 275-299 |
| 630R | 22 | PH | | | 15-1 | 26-17-11 | D04948P | | 30 | | D04852P | 10 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 20

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0606 | 286T0606 | | | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | |
| 630R | 22 | | PH | 14-11 | 26-17-11 | D04948P | | 30 | | D04852P | | 10 | | | 150-199, 275-299 |
| 631 | 24 | | PK | 24-0 | 25-33-11 | D04948P | | 31 | | TB0031Y | A003 | BJ | | | 050-099 |
| 631 | 24 | | PK | 24-8 | 25-33-11 | D04948P | | 31 | | TB0031Y | A003 | BJ | | | 150-199, 277-299 |
| 631 | 24 | | PK | 24-8 | 21-58-16 | D04948P | | 31 | | TB0031Y | A003 | BJ | | | 275-276 |
| 633R | 20 | | PH | 22-3 | 26-23-12 | D00866 | | 11 | | D04948P | | 33 | | | 150-199, 275-299 |
| 634R | 22 | | PH | 15-4 | 26-17-11 | D07994P | | 44 | | D04852P | | 6 | | | 050-099 |
| 634R | 22 | | PH | 15-2 | 26-17-11 | D07994P | | 44 | | D04852P | | 6 | | | 150-199, 275-299 |
| 635R | 20 | | PH | 2-7 | 26-17-11 | D07994P | | 45 | | GD00706 | A.. | 2 | | | ALL |
| 636R | 20 | | PH | 22-3 | 26-23-12 | D00866 | | 14 | | D04948P | | 49 | | | 155-199 |
| 636R | 20 | | PH | 22-3 | 26-23-12 | D00866 | | 14 | | D04948P | | 32 | | | 275-299 |
| 637 | 20 | | PA | 18-0 | 26-16-21 | D05214P | | 13 | | SM00135 | | 9 | | | 050-099 |
| 637 | 20 | | PA | 18-3 | 26-16-21 | D05214P | | 13 | | SM00135 | | 9 | | | 150-199, 275-299 |
| 638 | 20 | | PA | 24-3 | 26-16-21 | D04948P | | 24 | | SM00135 | | 9 | | | 050-099 |
| 638 | 20 | | PA | 24-7 | 26-16-21 | D04948P | | 24 | | SM00135 | | 9 | | | 150-199, 275-299 |
| 644 | 24 | | PK | 111-8 | 73-21-15 | D04852P | | 4 | | D05054J | | 11 | | | 050-099 |
| 644 | 24 | | PK | 132-1 | 73-21-15 | D04852P | | 4 | | D05054J | | 11 | | | 150-199, 275-299 |
| 718R | 20 | | PH | 14-11 | 26-23-12 | D04852P | | 18 | | D04948P | | 38 | | | 150-199, 275-299 |
| 719R | 20 | | PH | 15-1 | 26-23-12 | D04852P | | 19 | | D04948P | | 39 | | | 050-099 |
| 719R | 20 | | PH | 14-11 | 26-23-12 | D04852P | | 19 | | D04948P | | 39 | | | 150-199, 275-299 |
| 720R | 20 | | PH | 15-1 | 26-23-12 | D04852P | | 20 | | D04948P | | 40 | | | 050-099 |
| 720R | 20 | | PH | 14-11 | 26-23-12 | D04852P | | 20 | | D04948P | | 40 | | | 150-199, 275-299 |
| 721R | 20 | | PH | 3-2 | 26-23-12 | D10864 | | 3 | | GD00711 | D.. | 2 | | | 050-099 |
| 721R | 20 | | PH | 19-0 | 26-23-12 | D10864 | | 3 | | GD00711 | D.. | 2 | | | 150-154 |
| 721R | 20 | | PH | 18-2 | 26-23-12 | D10864 | | 3 | | GD00711 | D.. | 2 | | | 155-199, 280-299 |
| 721R | 20 | | PH | 18-2 | 26-23-11 | D10864 | | 3 | | GD00711 | D.. | 2 | | | 275-278 |
| 722R | 20 | | PH | 5-0 | 26-23-12 | D10864 | | 2 | | SM00099 | | 9 | | | 050-099 |
| 722R | 20 | | PH | 13-9 | 26-23-12 | D10864 | | 2 | | SM00099 | | 9 | | | 150-154 |
| 722R | 20 | | PH | 10-10 | 26-23-12 | D10864 | | 2 | | SM00099 | | 9 | | | 155-199, 280-299 |
| 722R | 20 | | PH | 10-10 | 26-23-11 | D10864 | | 2 | | SM00099 | | 9 | | | 275-278 |
| 723R | 20 | | PH | 6-7 | 26-23-12 | D10866 | | 3 | | GD00711 | D.. | 2 | | | 050-099 |
| 723R | 20 | | PH | 20-0 | 26-23-11 | D10866 | | 3 | | GD00711 | D.. | 2 | | | 150-154 |
| 723R | 20 | | PH | 19-5 | 26-23-12 | D10866 | | 3 | | GD00711 | D.. | 2 | | | 155-199, 280-299 |
| 723R | 20 | | PH | 19-5 | 26-23-11 | D10866 | | 3 | | GD00711 | D.. | 2 | | | 275-278 |
| 724R | 20 | | PH | 6-0 | 26-23-12 | D10866 | | 2 | | SM00099 | | 9 | | | 050-099 |
| 724R | 20 | | PH | 13-9 | 26-23-12 | D10866 | | 2 | | SM00099 | | 9 | | | 150-154 |
| 724R | 20 | | PH | 12-1 | 26-23-12 | D10866 | | 2 | | SM00099 | | 9 | | | 155-199, 280-299 |
| 724R | 20 | | PH | 12-1 | 26-23-11 | D10866 | | 2 | | SM00099 | | 9 | | | 275-278 |
| 729 | 24 | | PK | 18-7 | SPARE | D04852P | | | CAP | Y | | | CAP | Y | 051-099 |
| 729 | 24 | | PK | 18-4 | SPARE | D04852P | | | CAP | Y | | | CAP | Y | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 21

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | | |
|------------------------|-----------------|--|----|-----|-------------|----------|---------|------|------|--------|-------|------|------|---------|--|-------------|----|----|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | | |
| W0606 | 286T0606 | FIRE DET & LOWER LOBE CARGO SMOKE DETECTION (continued) | | | | | | | | | | | | | | | | | |
| 729 | 24 | | PK | | 18-4 | 21-44-21 | D04852P | | 24 | | | | | D00866 | | 24 | | | 275-276 |
| 730 | 24 | | PK | | 18-7 | SPARE | D04852P | | CAP | Y | | | | D00866 | | CAP | Y | | 051-099 |
| 730 | 24 | | PK | | 18-4 | SPARE | D04852P | | CAP | Y | | | | D00866 | | CAP | Y | | 150-154 |
| 730 | 24 | | PK | | 18-4 | 21-44-21 | D04852P | | | | 26 | | | D00866 | | | | 26 | 275-276 |
| 793 | 20 | | PQ | P3 | 14-4 | 28-22-21 | SP01748 | | | | | | | SP09728 | | | | S | 155, 163-164, 275-299 |
| 793Z | | | | P3 | 0-0 | 28-22-21 | SP01748 | | | | | | | SP09728 | | DED | | | 155, 163-164, 275-299 |
| A-A | | | | | 0-0 | 31-31-22 | S00668 | | ACOM | \$ | | | | SP03346 | | | | 9 | 050-099 |
| A-A | | | | | 0-0 | 31-31-22 | S00668 | | COM | \$ | | | | SP03346 | | | | 9 | 150-199, 275-299 |
| A-B | | | | | 0-0 | 31-31-22 | S00668 | | ANC | \$ | | | | SP00377 | | | | 9 | 050-099 |
| A-B | | | | | 0-0 | 31-31-22 | S00668 | | NC | \$ | | | | SP00377 | | | | 9 | 150-199, 275-299 |
| A-C | | | | | 0-0 | 31-31-22 | S00668 | | ANO | \$ | | | | SP03344 | | | | 9 | 050-099 |
| A-C | | | | | 0-0 | 31-31-22 | S00668 | | NO | \$ | | | | SP03344 | | | | 9 | 150-199, 275-299 |
| A-D | | | | | 0-0 | 31-31-22 | S00669 | | ACOM | \$ | | | | SP02772 | | | | 9 | 050-099 |
| A-D | | | | | 0-0 | 31-31-22 | S00669 | | COM | \$ | | | | SP02772 | | | | 9 | 150-199, 275-299 |
| A-E | | | | | 0-0 | 31-31-22 | S00669 | | ANO | \$ | | | | SP02774 | | | | 9 | 050-099 |
| A-E | | | | | 0-0 | 31-31-22 | S00669 | | NO | \$ | | | | SP02774 | | | | 9 | 150-199, 275-299 |
| A-F | | | | | 0-0 | 31-31-22 | S00669 | | ANC | \$ | | | | SP00377 | | | | 9 | 050-099 |
| A-F | | | | | 0-0 | 31-31-22 | S00669 | | NC | \$ | | | | SP00377 | | | | 9 | 150-199, 275-299 |
| W0608 | 286T0608 | WDO HTRS, PROBE HTRS | | | | | | | | | | | | | | | | | |
| 001 | 20 | | PA | | 28-0 | SPARE | D04968J | | | | 1 | | | D04338P | | | | 1 | ALL |
| 002 | 20 | | PA | | 28-0 | SPARE | D04968J | | | | 2 | | | D04338P | | | | 2 | ALL |
| 003 | 20 | | PA | | 28-0 | 33-42-21 | D04968J | | | | 3 | | | D04338P | | | | 3 | 050-099 |
| 003 | 18 | | PA | | 28-0 | 33-42-21 | D04968J | | | DL | 3 | | | D04338P | | | DL | 3 | 150-199, 275-299 |
| 004 | 22 | | PA | | 28-0 | SPARE | D04968J | | | | 4 | | | D04338P | | | | 4 | 150-199, 275-299 |
| 005 | 22 | | PA | | 28-0 | 30-21-11 | D04968J | | | | 5 | | | D04338P | | | | 5 | ALL |
| 006 | 22 | | PA | | 28-0 | 30-21-11 | D04968J | | | | 6 | | | D04338P | | | | 6 | ALL |
| 007 | 24 | | PK | | 28-0 | 30-21-11 | D04968J | | | | 7 | | | D04338P | | | | 7 | 050-099, 155-199, 275-299 |
| 007 | 22 | | PA | | 28-0 | 30-21-11 | D04968J | | | | 7 | | | D04338P | | | | 7 | 150-154 |
| 008 | 20 | | PA | | 28-0 | SPARE | D04968J | | | | 8 | | | D04338P | | | | 8 | ALL |
| 009 | 20 | | PA | | 28-0 | SPARE | D04968J | | | | 9 | | | D04338P | | | | 9 | ALL |
| 010 | 24 | | PK | | 28-0 | 33-42-21 | D04968J | | | | 10 | | | D04338P | | | | 10 | ALL |
| 013 | 20 | | PA | | 28-0 | 21-45-11 | D04968J | | | | 13 | | | D04338P | | | | 13 | ALL |
| 014 | 20 | | PA | | 28-0 | 21-45-11 | D04968J | | | | 14 | | | D04338P | | | | 14 | ALL |
| 015 | 24 | | PK | | 28-0 | 33-42-11 | D04968J | | | | 15 | | | D04338P | | | | 15 | ALL |
| 024 | 18 | | PA | | 28-0 | 33-42-11 | D04968J | | | DL | 24 | | | D04338P | | | DL | 24 | 050-099 |
| 024 | 16 | | PA | | 28-0 | 33-42-11 | D04968J | | | FL | 24 | | | D04338P | | | FL | 24 | 150-199, 275-299 |
| 027 | 16 | | PA | | 28-0 | 27-32-31 | D04968J | | | FL | 27 | | | D04338P | | | FL | 27 | ALL |

WIRE LIST

D280T132

91-21-11

Section W0600

Page 22

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|--|-----------------|----|----|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0608 | | 286T0608 | | | | | WDO HTRS,PROBE HTRS (continued) | | | | | | | | | |
| 078 | | 22 | | PA | | 28-0 | 30-21-11 | D04338P | | | | D04968J | | | | 050-099 |
| 078 | | 22 | | PA | | 28-0 | 30-21-11 | D04968J | | | | D04338P | | | | 150-199 |
| 079 | | 22 | | PA | | 28-0 | 30-21-11 | D04338P | | | | D04968J | | | | 050-099 |
| 079 | | 22 | | PA | | 28-0 | 30-21-11 | D04968J | | | | D04338P | | | | 150-199 |
| 080 | | 22 | | PA | | 28-0 | 30-21-11 | D04338P | | | | D04968J | | | | 050-099 |
| 080 | | 22 | | PA | | 28-0 | 30-21-11 | D04968J | | | | D04338P | | | | 150-199 |
| 082 | | 22 | | PA | | 28-0 | 30-21-11 | D04338P | | | | D04968J | | | | 050-099 |
| 082 | | 22 | | PA | | 28-0 | 30-21-11 | D04968J | | | | D04338P | | | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0600
Page 23 End
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0610 | 286T0610 | | | WING & ENGINE/NOSE COWL THERMAL ANTI-ICE | | | | | | | | | | | | |
| 001 | 20 | PA | | 23-0 | SPARE | D04972J | | 1 | | | | D04340P | | 1 | | ALL |
| 002 | 22 | PA | | 23-0 | SPARE | D04972J | | 2 | | | | D04340P | | 2 | | ALL |
| 004 | 22 | PA | | 23-0 | 33-45-11 | D04972J | | 4 | | | | D04340P | | 4 | | ALL |
| 005 | 22 | PA | | 23-0 | SPARE | D04972J | | 5 | | | | D04340P | | 5 | | 150-154 |
| 005 | 22 | PA | | 23-0 | 30-21-11 | D04972J | | 5 | | | | D04340P | | 5 | | 275-299 |
| 006 | 22 | PA | | 23-0 | 30-21-11 | D04972J | | 6 | | | | D04340P | | 6 | | ALL |
| 007 | 24 | PK | | 23-0 | 30-21-11 | D04972J | | 7 | | | | D04340P | | 7 | | ALL |
| 009 | 20 | PA | | 23-0 | 33-43-11 | D04972J | | 9 | | | | D04340P | | 9 | | 050-099 |
| 009 | 18 | PA | | 23-0 | 33-43-11 | D04972J | | 9 | DL | | | D04340P | | 9 | DL | 150-199, 275-299 |
| 011 | 20 | PA | | 23-0 | 33-42-21 | D04972J | | 11 | | | | D04340P | | 11 | | 050-099 |
| 011 | 18 | PA | | 23-0 | 33-42-21 | D04972J | | 11 | DL | | | D04340P | | 11 | DL | 150-199, 275-299 |
| 012 | 20 | PA | | 23-0 | 33-44-11 | D04340P | | 12 | | | | D04972J | | 12 | | ALL |
| 013 | 20 | PA | | 23-0 | 21-45-11 | D04340P | | 13 | | | | D04972J | | 13 | | ALL |
| 014 | 20 | PA | | 23-0 | 21-45-11 | D04340P | | 14 | | | | D04972J | | 14 | | ALL |
| 024 | 18 | PA | | 23-0 | 33-42-11 | D04972J | | 24 | DL | | | D04340P | | 24 | DL | 050-099 |
| 024 | 16 | PA | | 23-0 | 33-42-11 | D04972J | | 24 | FL | | | D04340P | | 24 | FL | 150-199, 275-299 |
| 025 | 20 | PA | | 23-0 | 33-42-11 | D04972J | | 25 | | | | D04340P | | 25 | | ALL |
| 027 | 22 | PA | | 23-0 | 30-21-11 | D04340P | | 16 | | | | D04972J | | 16 | | 050-099 |
| 027 | 22 | PA | | 23-0 | 30-21-11 | D04972J | | 16 | | | | D04340P | | 16 | | 150-199 |
| 028 | 22 | PA | | 23-0 | 30-21-11 | D04340P | | 17 | | | | D04972J | | 17 | | 050-099 |
| 028 | 22 | PA | | 23-0 | 30-21-11 | D04972J | | 17 | | | | D04340P | | 17 | | 150-199 |
| 029 | 22 | PA | | 23-0 | 30-21-11 | D04340P | | 18 | | | | D04972J | | 18 | | 050-099 |
| 029 | 22 | PA | | 23-0 | 30-21-11 | D04972J | | 18 | | | | D04340P | | 18 | | 150-199 |
| 030 | 22 | PA | | 23-0 | 30-21-11 | D04340P | | 19 | | | | D04972J | | 19 | | 050-099 |
| 030 | 22 | PA | | 23-0 | 30-21-11 | D04972J | | 19 | | | | D04340P | | 19 | | 150-199 |
| 031 | 22 | PA | | 23-0 | 30-21-11 | D04340P | | 20 | | | | D04972J | | 20 | | 050-099 |
| 031 | 22 | PA | | 23-0 | 30-21-11 | D04972J | | 20 | | | | D04340P | | 20 | | 150-199 |
| W0611 | 286T0611 | | | PITCH SERVO ACTR | | | | | | | | | | | | |
| 001 | 20 | UA | | 33-4 | 22-11-32 | D00189 | | 2 | | | | D04481J | | 1 | | ALL |
| 002 | 20 | UA | | 33-4 | 22-11-32 | D04481J | | 14 | | | | D00189 | | 18 | | ALL |
| 003 | 18 | UA | | 2-3 | 22-11-32 | D00189 | | 17 | | | | GD00189 | | D.. | N | ALL |
| 004 | 18 | UA | | 2-3 | 22-11-32 | D00189 | | 1 | | | | GD00189 | | D.. | N | ALL |
| 005 | 18 | UA | | 2-4 | 22-11-32 | D00189 | | 19 | | | | GD00191 | | S.. | N | ALL |
| 201B | 20 | UB | IA | 33-3 | 22-11-31 | D04481J | | 5 | | | | SM00002 | | 9 | | ALL |
| 201R | 20 | UB | IA | 0-0 | 22-11-31 | D04481J | | 4 | | | | SM00001 | | 9 | | ALL |
| 203B | 20 | UB | IC | 0-8 | 22-11-31 | D00189 | | 7 | | | | SM00002 | | 9 | | ALL |
| 203R | 20 | UB | IC | 0-0 | 22-11-31 | D00189 | | 8 | | | | SM00001 | | 9 | | ALL |
| 204B | 20 | UB | ID | 0-8 | 22-11-31 | D00189 | | 12 | | | | SM00002 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0610

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0611 | 286T0611 | | | PITCH SERVO ACTR (continued) | | | | | | | | | | | |
| 204R | 20 | UB | ID | | 0-0 | 22-11-31 | D00189 | | | | SM00001 | | 9 | | ALL |
| 207B | 20 | UB | IG | | 33-3 | 22-12-31 | D04481J | | | | SM00006 | | 9 | | ALL |
| 207R | 20 | UB | IG | | 0-0 | 22-12-31 | D04481J | | | | SM00005 | | 9 | | ALL |
| 208B | 20 | UB | IH | | 0-8 | 22-12-31 | D00189 | | | | SM00006 | | 9 | | ALL |
| 208R | 20 | UB | IH | | 0-0 | 22-12-31 | D00189 | | | | SM00005 | | 9 | | ALL |
| 209B | 20 | UB | II | | 0-8 | 22-12-31 | D00189 | | | | SM00006 | | 9 | | ALL |
| 209R | 20 | UB | II | | 0-0 | 22-12-31 | D00189 | | | | SM00005 | | 9 | | ALL |
| 301B | 20 | UC | MA | | 33-4 | 22-12-31 | D04481J | | | | D00189 | | 15 | | ALL |
| 301R | 20 | UC | MA | | 0-0 | 22-12-31 | D04481J | | | | D00189 | | 14 | | ALL |
| 301Y | 20 | UC | MA | | 0-0 | 22-12-31 | D04481J | | | | D00189 | | 16 | | ALL |
| 302B | 20 | UC | MB | | 33-4 | 22-12-31 | D04481J | | | | D00189 | | 10 | | ALL |
| 302R | 20 | UC | MB | | 0-0 | 22-12-31 | D04481J | | | | D00189 | | 9 | | ALL |
| 302Y | 20 | UC | MB | | 0-0 | 22-12-31 | D04481J | | | | D00189 | | 11 | | ALL |
| W0612 | 286T0612 | | | AIR COND RIGHT PACK TEMP CONTROL | | | | | | | | | | | |
| 001 | 20 | UA | | | 27-9 | 21-53-21 | D08048P | | | | D00728 | | 3 | | ALL |
| 002 | 20 | UA | | | 27-9 | 21-53-21 | D08048P | | | | D00728 | | 2 | | ALL |
| 003 | 20 | UA | | | 21-4 | 21-53-21 | D08048P | | | | D00718 | | 3 | | ALL |
| 004 | 20 | UA | | | 21-4 | 21-53-21 | D08048P | | | | D00718 | | 2 | | ALL |
| 005 | 20 | UA | | | 22-7 | 21-53-21 | D08048P | | | | D00722 | | 1 | | ALL |
| 006 | 20 | UA | | | 22-7 | 21-53-21 | D08048P | | | | D00722 | | 2 | | ALL |
| 007 | 18 | UA | | | 4-7 | 21-53-21 | D00722 | | 3 | DK | GD00904 | A.. | N | | ALL |
| 008 | 18 | UA | | | 7-0 | 21-53-21 | D00728 | | 1 | DK | GD00906 | A.. | N | | ALL |
| 009 | 18 | UA | | | 7-7 | 21-53-21 | D00718 | | 1 | DK | GD00904 | A.. | N | | ALL |
| 010 | 20 | UA | | | 22-9 | 21-53-22 | D08066P | | 3 | | D00722 | | 6 | | ALL |
| 011 | 18 | UA | | | 4-3 | 21-53-22 | D00722 | | 8 | DK | GD00912 | D.. | N | | ALL |
| 012 | 20 | UA | | | 22-9 | 21-53-22 | D08066P | | 4 | | D00722 | | 9 | | ALL |
| 013 | 18 | UA | | | 4-3 | 21-53-22 | D00722 | | 11 | DK | GD00912 | D.. | N | | ALL |
| 014 | 18 | UA | | | 4-4 | 21-53-22 | D00722 | | 13 | DK | GD00914 | S.. | N | | ALL |
| 015 | 20 | UA | | | 21-6 | 21-53-22 | D08066P | | 1 | | D00718 | | 13 | | ALL |
| 016 | 18 | UA | | | 7-2 | 21-53-22 | D00718 | | 15 | DK | GD00912 | D.. | N | | ALL |
| 017 | 20 | UA | | | 21-6 | 21-53-22 | D08066P | | 2 | | D00718 | | 16 | | ALL |
| 018 | 18 | UA | | | 7-2 | 21-53-22 | D00718 | | 18 | DK | GD00912 | D.. | N | | ALL |
| 019 | 18 | UA | | | 7-3 | 21-53-22 | D00718 | | 19 | DK | GD00914 | S.. | N | | ALL |
| 020 | 20 | UA | | | 27-11 | 21-53-22 | D08066P | | 5 | | D00728 | | 13 | | ALL |
| 021 | 18 | UA | | | 6-4 | 21-53-22 | D00728 | | 15 | DK | GD00920 | D.. | N | | ALL |
| 022 | 20 | UA | | | 27-11 | 21-53-22 | D08066P | | 6 | | D00728 | | 16 | | ALL |
| 023 | 18 | UA | | | 6-4 | 21-53-22 | D00728 | | 18 | DK | GD00920 | D.. | N | | ALL |
| 024 | 18 | UA | | | 6-9 | 21-53-22 | D00728 | | 19 | DK | GD00922 | S.. | N | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0610
 Page 2
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|---|-------|------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0612 | 286T0612 | AIR COND RIGHT PACK TEMP CONTROL (continued) | | | | | | | | | | | | | |
| 025 | 20 | | UA | 27-3 | 36-11-21 | D05056P | 19 | | | | D01282 | 1 | | | ALL |
| 026 | 20 | | UA | 27-3 | 36-11-21 | D05056P | 20 | | | | D01282 | 2 | | | ALL |
| 027 | 20 | | UA | 27-3 | 36-11-21 | D05056P | 21 | | | | D01282 | 4 | | | ALL |
| 028 | 20 | | UA | 27-3 | 36-11-21 | D05056P | 22 | | | | D01282 | 7 | | | ALL |
| 029 | 18 | | UA | 5-1 | 36-11-21 | D01282 | 5 | | | | GD00920 | D.. | N | | ALL |
| 030 | 18 | | UA | 5-1 | 36-11-21 | D01282 | 6 | | | | GD00920 | D.. | N | | ALL |
| 031 | 18 | | UA | 6-4 | 36-11-21 | D01282 | 3 | | | | GD00906 | A.. | N | | ALL |
| 032R | 18 | | XG | 29-1 | 26-18-21 | D08066P | 8 | DL | | | D01460 | =1 | | | ALL |
| 201B | 20 | | UB | H | 22-0 | 21-51-23 | D08066P | 13 | | | D10138 | 1 | | | ALL |
| 201R | 20 | | UB | H | 0-0 | 21-51-23 | D08066P | 14 | | | D10138 | 2 | | | ALL |
| 202B | 20 | | UB | I | 23-8 | 21-51-23 | D08066P | 15 | | | D10140 | 1 | | | ALL |
| 202R | 20 | | UB | I | 0-0 | 21-51-23 | D08066P | 16 | | | D10140 | 2 | | | ALL |
| 301B | 20 | | UC | A | 22-8 | 21-53-21 | D05056P | 1 | | | D00722 | 5 | | | ALL |
| 301R | 20 | | UC | A | 0-0 | 21-53-21 | D05056P | 2 | | | D00722 | 4 | | | ALL |
| 301Y | 20 | | UC | A | 0-0 | 21-53-21 | D05056P | 3 | | | D00722 | 12 | | | ALL |
| 302B | 20 | | UC | B | 27-11 | 21-53-21 | D05056P | 4 | | | D00728 | 10 | | | ALL |
| 302R | 20 | | UC | B | 0-0 | 21-53-21 | D05056P | 5 | | | D00728 | 11 | | | ALL |
| 302Y | 20 | | UC | B | 0-0 | 21-53-21 | D05056P | 6 | | | D00728 | 12 | | | ALL |
| 303B | 20 | | UC | C | 21-5 | 21-53-21 | D05056P | 7 | | | D00718 | 10 | | | ALL |
| 303R | 20 | | UC | C | 0-0 | 21-53-21 | D05056P | 8 | | | D00718 | 11 | | | ALL |
| 303Y | 20 | | UC | C | 0-0 | 21-53-21 | D05056P | 9 | | | D00718 | 12 | | | ALL |
| 305B | 20 | | UC | D | 21-5 | 21-52-21 | D05056P | 10 | | | D00718 | 7 | | | ALL |
| 305R | 20 | | UC | D | 0-0 | 21-52-21 | D05056P | 11 | | | D00718 | 8 | | | ALL |
| 305Y | 20 | | UC | D | 0-0 | 21-52-21 | D05056P | 12 | | | D00718 | 9 | | | ALL |
| 306B | 20 | | UC | E | 21-5 | 21-51-22 | D05056P | 13 | | | D00718 | 6 | | | ALL |
| 306R | 20 | | UC | E | 0-0 | 21-51-22 | D05056P | 14 | | | D00718 | 5 | | | ALL |
| 306Y | 20 | | UC | E | 0-0 | 21-51-22 | D05056P | 15 | | | D00718 | 4 | | | ALL |
| 307B | 20 | | UC | F | 27-11 | 21-51-22 | D05056P | 16 | | | D00728 | 6 | | | ALL |
| 307R | 20 | | UC | F | 0-0 | 21-51-22 | D05056P | 17 | | | D00728 | 5 | | | ALL |
| 307Y | 20 | | UC | F | 0-0 | 21-51-22 | D05056P | 18 | | | D00728 | 4 | | | ALL |
| 308B | 20 | | UC | G | 27-11 | 21-52-21 | D05056P | 25 | | | D00728 | 7 | | | 050-099 |
| 308B | 20 | | UC | MH | 27-11 | 21-52-21 | D05056P | 25 | | | D00728 | 7 | | | 150-199, 275-299 |
| 308R | 20 | | UC | G | 0-0 | 21-52-21 | D05056P | 26 | | | D00728 | 8 | | | 050-099 |
| 308R | 20 | | UC | MH | 0-0 | 21-52-21 | D05056P | 26 | | | D00728 | 8 | | | 150-199, 275-299 |
| 308Y | 20 | | UC | G | 0-0 | 21-52-21 | D05056P | 27 | | | D00728 | 9 | | | 050-099 |
| 308Y | 20 | | UC | MH | 0-0 | 21-52-21 | D05056P | 27 | | | D00728 | 9 | | | 150-199, 275-299 |
| W0614 | 286T0614 | FIRE DET-APU LOOP 1 & L WW,BULK & AFT CAR. | | | | | | | | | | | | | |
| 003 | 22 | | PA | 88-5 | 28-25-21 | D05700J | 3 | | | | D05270P | 3 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0610

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|--------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0614 | 286T0614 | | | FIRE DET-APU LOOP 1 & L WW,BULK & AFT CAR. (continued) | | | | | | | | | | | |
| 003 | 20 | | PA | 98-10 | 28-25-21 | D05700J | | 3 | | | D05270P | | 3 | | 150-199, 275-299 |
| 004 | 22 | | PA | 88-5 | 28-25-21 | D05700J | | 4 | | | D05270P | | 4 | | 050-099 |
| 004 | 20 | | PA | 98-10 | 28-25-21 | D05700J | | 4 | | | D05270P | | 4 | | 150-199, 275-299 |
| 005 | 20 | | PA | 88-5 | 27-11-12 | D05270P | | 5 | | | D05700J | | 5 | | 050-099 |
| 005 | 20 | | PA | 98-10 | 27-11-12 | D05270P | | 5 | | | D05700J | | 5 | | 150-199, 275-299 |
| 006 | 18 | | PA | 88-5 | 27-11-12 | D05270P | | 6 | DK | | D05700J | | 6 | | 050-099 |
| 006 | 18 | | PA | 98-10 | 27-11-12 | D05270P | | 6 | DK | | D05700J | | 6 | | 150-199, 275-299 |
| 007 | 18 | | PA | 13-4 | 33-13-18 | D00864 | | 1 | DK | | SP02284 | | 9 | | 050-099, 150-155, 162-165, 275-276 |
| 008 | 18 | | PA | 3-6 | 33-13-18 | D00864 | | 2 | DK | | GD04452 | A.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 009R | 20 | | PH | 2-3 | 26-11-11 | D10104 | | 6 | | | GD04474 | D.. | 2 | | ALL |
| 010 | 18 | | PA | 88-5 | 27-11-12 | D05270P | | 10 | DK | | D05700J | | 10 | | 050-099 |
| 010 | 18 | | PA | 98-10 | 27-11-12 | D05270P | | 10 | DK | | D05700J | | 10 | | 150-199, 275-299 |
| 011 | 20 | | PA | 88-5 | 27-11-12 | D05270P | | 11 | | | D05700J | | 11 | | 050-099 |
| 011 | 20 | | PA | 98-10 | 27-11-12 | D05270P | | 11 | | | D05700J | | 11 | | 150-199, 275-299 |
| 012 | 18 | | PA | 5-0 | 27-11-12 | D05700J | | 2 | | | GD00788 | D.. | 2 | | ALL |
| 013R | 20 | | PH | 13-1 | 26-22-21 | D00864 | | 19 | | | SP02480 | | 9 | | 275-299 |
| 014 | 20 | | PA | 4-9 | 33-13-18 | D10104 | | 1 | | | SP02280 | | 9 | | 050-099, 150-155, 162-165, 275-276 |
| 015 | 20 | | PA | 2-3 | 33-13-18 | D10104 | | 2 | | | GD04474 | A.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 018 | 20 | | PA | 5-0 | 28-21-13 | D05700J | | 15 | | | GD00788 | D.. | 2 | | ALL |
| 019 | 20 | | PQ | AA | 28-4 | 28-22-21 | D00836 | 32 | | | SP01750 | | S | | 050-099, 150-154, 156-162, 165-199 |
| 019 | 20 | | PQ | AA | 9-8 | 28-22-21 | D00836 | 32 | | | SP09730 | | S | | 155, 163-164, 275-299 |
| 019Z | | | | AA | 0-0 | 28-22-21 | D00836 | DED | | | SP01750 | DED | | | 050-099, 150-154, 156-162, 165-199 |
| 019Z | | | | AA | 0-0 | 28-22-21 | D00836 | DED | | | SP09730 | DED | | | 155, 163-164, 275-299 |
| 020 | 20 | | PA | 5-0 | 28-21-13 | D05700J | | 16 | | | GD00788 | D.. | 2 | | ALL |
| 024 | 22 | | PA | 94-4 | 31-31-22 | D05700J | | 1 | | | SP03262 | | S | | 050-099 |
| 024 | 22 | | PA | 51-7 | 31-31-22 | D05700J | | 1 | | | SP03262 | | S | | 150-199, 275-299 |
| 025R | 20 | | PH | 5-4 | 26-16-11 | D01456 | | 10 | | | GD00106 | S.. | 2 | | ALL |
| 026R | 24 | | PP | 15-8 | 26-16-11 | D05042P | | 7 | | | D07990P | | 31 | | ALL |
| 027R | 20 | | PH | 2-8 | 26-16-11 | D07990P | | 32 | | | GD04462 | D.. | 2 | | ALL |
| 028R | 24 | | PP | 34-7 | 26-16-11 | D01456 | | 4 | | | D07990P | | 33 | | ALL |
| 029R | 20 | | PH | 5-4 | 26-16-11 | D01456 | | 9 | | | GD00106 | D.. | 2 | | ALL |
| 030R | 24 | | PP | 34-7 | 26-16-11 | D01456 | | 12 | | | D07990P | | 36 | | ALL |
| 031R | 24 | | PP | 34-7 | 26-16-11 | D01456 | | 11 | | | D07990P | | 35 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0610

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|--------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0614 | 286T0614 | | | FIRE DET-APU LOOP 1 & L WW,BULK & AFT CAR. (continued) | | | | | | | | | | | | |
| 032R | 20 | | PH | | 5-4 | 26-16-11 | D01456 | | 5 | | | GD00106 | D.. | 2 | | ALL |
| 033R | 22 | | PH | | 16-7 | 26-16-11 | D00864 | | 12 | | | D07990P | | 39 | | ALL |
| 034R | 24 | | PP | | 136-0 | 26-16-11 | D01458 | | 4 | | | D07990P | | 34 | | 050-099 |
| 034R | 24 | | PP | | 157-11 | 26-16-11 | D01458 | | 4 | | | D07990P | | 34 | | 150-154 |
| 034R | 24 | | PP | | 158-0 | 26-16-11 | D01458 | | 4 | | | D07990P | | 34 | | 155-199, 275-299 |
| 035R | 20 | | PH | | 4-8 | 26-16-11 | D01458 | | 9 | | | GD00108 | D.. | 2 | | 050-099 |
| 035R | 20 | | PH | | 4-7 | 26-16-11 | D01458 | | 9 | | | GD00108 | D.. | 2 | | 150-199, 275-299 |
| 036R | 24 | | PP | | 136-0 | 26-16-11 | D01458 | | 12 | | | D07990P | | 38 | | 050-099 |
| 036R | 24 | | PP | | 157-11 | 26-16-11 | D01458 | | 12 | | | D07990P | | 38 | | 150-154 |
| 036R | 24 | | PP | | 158-0 | 26-16-11 | D01458 | | 12 | | | D07990P | | 38 | | 155-199, 275-299 |
| 037R | 24 | | PP | | 136-0 | 26-16-11 | D01458 | | 11 | | | D07990P | | 37 | | 050-099 |
| 037R | 24 | | PP | | 157-11 | 26-16-11 | D01458 | | 11 | | | D07990P | | 37 | | 150-154 |
| 037R | 24 | | PP | | 158-0 | 26-16-11 | D01458 | | 11 | | | D07990P | | 37 | | 155-199, 275-299 |
| 038R | 20 | | PH | | 4-8 | 26-16-11 | D01458 | | 5 | | | GD00108 | D.. | 2 | | 050-099 |
| 038R | 20 | | PH | | 4-7 | 26-16-11 | D01458 | | 5 | | | GD00108 | D.. | 2 | | 150-199, 275-299 |
| 039R | 20 | | PH | | 4-8 | 26-16-11 | D01458 | | 10 | | | GD00108 | S.. | 2 | | 050-099 |
| 039R | 20 | | PH | | 4-7 | 26-16-11 | D01458 | | 10 | | | GD00108 | S.. | 2 | | 150-199, 275-299 |
| 041R | 22 | | PH | | 15-8 | 26-11-11 | D07990P | | 1 | | | D05042P | | 11 | | ALL |
| 042R | 20 | | PH | | 2-8 | 26-11-11 | D07990P | | 2 | | | GD00706 | D.. | 2 | | ALL |
| 044R | 22 | | PH | | 15-8 | 26-11-11 | D07990P | | 4 | | | D05042P | | 14 | | ALL |
| 045R | 22 | | PH | | 16-10 | 26-11-11 | D07990P | | 5 | | | D10104 | | 8 | | ALL |
| 046R | 22 | | PH | | 70-11 | 26-11-11 | D07990P | | 6 | | | D04546J | | 1 | | 050-099 |
| 046R | 22 | | PH | | 81-4 | 26-11-11 | D07990P | | 6 | | | D04546J | | 1 | | 150-199, 275-299 |
| 047R | 22 | | PH | | 70-11 | 26-11-11 | D07990P | | 7 | | | D04546J | | 2 | | 050-099 |
| 047R | 22 | | PH | | 81-4 | 26-11-11 | D07990P | | 7 | | | D04546J | | 2 | | 150-199, 275-299 |
| 048R | 22 | | PH | | 70-11 | 26-11-11 | D07990P | | 8 | | | D04546J | | 3 | | 050-099 |
| 048R | 22 | | PH | | 81-4 | 26-11-11 | D07990P | | 8 | | | D04546J | | 3 | | 150-199, 275-299 |
| 049R | 20 | | PH | | 2-8 | 26-11-11 | D07990P | | 9 | | | GD00706 | D.. | 2 | | ALL |
| 050R | 22 | | PH | | 16-10 | 26-11-11 | D10104 | | 7 | | | D07990P | | 10 | | ALL |
| 051R | 22 | | PH | | 15-8 | 26-11-12 | D07990P | | 11 | | | D05042P | | 16 | | ALL |
| 052R | 20 | | PH | | 2-8 | 26-11-12 | D07990P | | 12 | | | GD00706 | D.. | 2 | | ALL |
| 054R | 22 | | PH | | 16-8 | 26-11-12 | D07990P | | 14 | | | D10100 | | 1 | | ALL |
| 055R | 22 | | PH | | 16-10 | 26-11-12 | D07990P | | 15 | | | D10104 | | 9 | | ALL |
| 056R | 22 | | PH | | 70-11 | 26-11-12 | D07990P | | 17 | | | D04546J | | 4 | | 050-099 |
| 056R | 22 | | PH | | 81-4 | 26-11-12 | D07990P | | 17 | | | D04546J | | 4 | | 150-199, 275-299 |
| 057R | 22 | | PH | | 70-11 | 26-11-12 | D07990P | | 18 | | | D04546J | | 9 | | 050-099 |
| 057R | 22 | | PH | | 81-4 | 26-11-12 | D07990P | | 18 | | | D04546J | | 9 | | 150-199, 275-299 |
| 058R | 22 | | PH | | 70-11 | 26-11-12 | D07990P | | 16 | | | D04546J | | 8 | | 050-099 |
| 058R | 22 | | PH | | 81-4 | 26-11-12 | D07990P | | 16 | | | D04546J | | 8 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0610

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|---------|-------|------|------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0614 | 286T0614 | | | FIRE DET-APU LOOP 1 & L WW,BULK & AFT CAR. (continued) | | | | | | | | | | | |
| 059R | 20 | | PH | | 2-8 | 26-11-12 | D07990P | | 19 | | GD00706 | D.. | 2 | | ALL |
| 061R | 22 | | PH | | 15-8 | 26-15-11 | D07990P | | 21 | | D05042P | | 21 | | ALL |
| 062R | 22 | | PH | | 15-8 | 26-11-11 | D07990P | | 22 | | D05042P | | 15 | | ALL |
| 063R | 22 | | PH | | 16-10 | 26-11-11 | D07990P | | 23 | | D10104 | | 5 | | ALL |
| 064 | 22 | | PA | | 21-2 | 31-31-26 | D05042P | | 24 | | TB0255X | A001 | BJ | | ALL |
| 064R | 22 | | PH | | 15-8 | SPARE | D07990P | | 24 | | D05042P | | 49 | | 275-276 |
| 064R | 22 | | PH | | 15-8 | SPARE | D07990P | | 24 | | D05042P | | 44 | | 277-299 |
| 065R | 22 | | PH | | 16-10 | 26-15-11 | D07990P | | 25 | | D10104 | | 10 | | ALL |
| 066R | 22 | | PH | | 116-0 | 26-15-11 | D07990P | | 27 | | D06112P | | 2 | | 050-099 |
| 066R | 22 | | PH | | 136-8 | 26-15-11 | D07990P | | 27 | | D06112P | | 2 | | 150-154 |
| 066R | 22 | | PH | | 136-9 | 26-15-11 | D07990P | | 27 | | D06112P | | 2 | | 155-199, 275-299 |
| 067R | 22 | | PH | | 116-0 | 26-15-11 | D07990P | | 28 | | D06112P | | 1 | | 050-099 |
| 067R | 22 | | PH | | 136-8 | 26-15-11 | D07990P | | 28 | | D06112P | | 1 | | 150-154 |
| 067R | 22 | | PH | | 136-9 | 26-15-11 | D07990P | | 28 | | D06112P | | 1 | | 155-199, 275-299 |
| 068R | 22 | | PH | | 116-0 | 26-15-11 | D07990P | | 26 | | D06112P | | 3 | | 050-099 |
| 068R | 22 | | PH | | 136-8 | 26-15-11 | D07990P | | 26 | | D06112P | | 3 | | 150-154 |
| 068R | 22 | | PH | | 136-9 | 26-15-11 | D07990P | | 26 | | D06112P | | 3 | | 155-199, 275-299 |
| 069R | 20 | | PH | | 2-8 | 26-15-11 | D07990P | | 29 | | GD00706 | D.. | 2 | | ALL |
| 070R | 22 | | PH | | 16-10 | 26-15-11 | D07990P | | 30 | | D10104 | | 14 | | ALL |
| 072R | 24 | | PP | | 16-10 | 26-16-11 | D10104 | | 11 | | D07990P | | 43 | | ALL |
| 076R | 20 | | PH | | 19-4 | 26-23-11 | D00864 | | 17 | | D05042P | | 26 | | ALL |
| 078R | 20 | | PH | | 7-0 | 26-21-11 | D05042P | | 3 | | SM00011 | | 9 | | ALL |
| 079R | 20 | | PH | | 41-1 | 26-21-11 | D05042P | | 4 | | SM00084 | | 9 | | 050-099 |
| 079R | 20 | | PH | | 51-11 | 26-21-11 | D05042P | | 4 | | SM00084 | | 9 | | 150-154 |
| 079R | 20 | | PH | | 52-0 | 26-21-11 | D05042P | | 4 | | SM00084 | | 9 | | 155-199, 275-299 |
| 080R | 20 | | PH | | 19-4 | 26-23-11 | D00864 | | 16 | | D05042P | | 5 | | ALL |
| 081R | 20 | | PH | | 19-4 | 26-23-11 | D00864 | | 20 | | D05042P | | 6 | | ALL |
| 082 | 20 | | PA | | 15-8 | 25-33-11 | D05042P | | 49 | | D05270P | | 41 | | 050-099, 155-199, 277-299 |
| 083R | 20 | | PH | | 14-4 | 26-21-11 | D00836 | | 23 | | SM00011 | | 9 | | ALL |
| 084R | 20 | | PH | | 48-11 | 26-21-11 | SP02302 | | 9 | | SM00084 | | 9 | | 050-099 |
| 084R | 20 | | PH | | 59-9 | 26-21-11 | SP02302 | | 9 | | SM00084 | | 9 | | 150-199, 275-299 |
| 085R | 20 | | PH | | 46-11 | 26-21-11 | D06886P | | 5 | | SM00011 | | 9 | | 050-099 |
| 085R | 20 | | PH | | 59-0 | 26-21-11 | D06886P | | 5 | | SM00011 | | 9 | | 150-154 |
| 085R | 20 | | PH | | 53-9 | 26-21-11 | D06886P | | 5 | | SM00011 | | 9 | | 155-199, 275-299 |
| 088R | 20 | | PH | | 12-10 | 26-21-11 | D06886P | | 7 | | SM00084 | | 9 | | 050-099 |
| 088R | 20 | | PH | | 10-0 | 26-21-11 | D06886P | | 7 | | SM00084 | | 9 | | 150-154 |
| 088R | 20 | | PH | | 8-9 | 26-21-11 | D06886P | | 7 | | SM00084 | | 9 | | 155-199, 275-299 |
| 091R | 20 | | PH | | 12-10 | 26-21-11 | D06886P | | 3 | | SM00091 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0610

Page 6

Mar 14/2007



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|-------|------|------|--------|-------------|----|---|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0614 | 286T0614 | | | FIRE DET-APU LOOP 1 & L WW,BULK & AFT CAR. (continued) | | | | | | | | | | | | | | | | |
| 091R | 20 | | PH | | 10-0 | 26-21-11 | D06886P | | 3 | | | | | | | SM00091 | 9 | | | 150-154 |
| 091R | 20 | | PH | | 8-9 | 26-21-11 | D06886P | | 3 | | | | | | | SM00091 | 9 | | | 155-199, 275-299 |
| 093R | 20 | | PH | | 61-0 | 26-23-11 | D06880P | | 9 | | | | | | | D00864 | 22 | | | 050-099 |
| 093R | 20 | | PH | | 65-0 | 26-23-11 | D06894P | | 8 | | | | | | | D00864 | 22 | | | 150-154 |
| 093R | 20 | | PH | | 64-9 | 26-23-11 | D06894P | | 8 | | | | | | | D00864 | 22 | | | 155-199, 275-299 |
| 096R | 20 | | PH | | 61-0 | 26-23-11 | D06880P | | 12 | | | | | | | D00864 | 5 | | | 050-099 |
| 096R | 20 | | PH | | 67-0 | 26-23-11 | D06894P | | 11 | | | | | | | D00864 | 5 | | | 150-154 |
| 096R | 20 | | PH | | 64-9 | 26-23-11 | D06894P | | 11 | | | | | | | D00864 | 5 | | | 155-199, 275-299 |
| 099R | 20 | | PH | | 13-0 | 26-23-11 | D06880P | | 6 | | | | | | | SM00099 | 9 | | | 050-099 |
| 099R | 20 | | PH | | 9-0 | 26-23-11 | D06894P | | 5 | | | | | | | SM00099 | 9 | | | 150-154 |
| 099R | 20 | | PH | | 8-0 | 26-23-11 | D06894P | | 5 | | | | | | | SM00099 | 9 | | | 155-199, 275-299 |
| 102 | 24 | | PK | | 15-8 | 29-21-31 | D05042P | | 30 | | | | | | | D05270P | 19 | | | ALL |
| 103 | 24 | | PK | | 15-8 | 29-21-31 | D05042P | | 35 | | | | | | | D05270P | 20 | | | ALL |
| 105 | 24 | | PK | | 15-8 | 29-21-31 | D05042P | | 8 | | | | | | | D05270P | 1 | | | ALL |
| 106 | 24 | | PK | | 15-8 | 29-21-31 | D05042P | | 17 | | | | | | | D05270P | 7 | | | ALL |
| 107 | 24 | | PK | | 15-8 | 29-21-31 | D05042P | | 18 | | | | | | | D05270P | 8 | | | ALL |
| 108 | 24 | | PK | | 15-8 | 29-21-31 | D05042P | | 9 | | | | | | | D05270P | 9 | | | ALL |
| 109 | 22 | | PA | | 15-8 | 28-25-11 | D05042P | | 20 | | | | | | | D05270P | 16 | | | 050-099 |
| 109 | 20 | | PA | | 15-8 | 28-25-11 | D05042P | | 20 | | | | | | | D05270P | 16 | | | 150-199, 275-299 |
| 110 | 24 | | PK | | 15-8 | 28-25-11 | D05042P | | 22 | | | | | | | D05270P | 18 | | | ALL |
| 111 | 20 | | PA | | 7-0 | 28-21-13 | SP01546 | | | | S | | | | | D05700J | 12 | | | 050-099 |
| 111 | 20 | | PA | | 7-2 | 28-21-13 | SP01546 | | | | S | | | | | D05700J | 12 | | | 150-199, 275-299 |
| 112 | 22 | | PA | | 7-0 | 28-21-13 | SP01548 | | | | S | | | | | D05700J | 13 | | | 050-099 |
| 112 | 22 | | PA | | 7-2 | 28-21-13 | SP01548 | | | | S | | | | | D05700J | 13 | | | 150-199, 275-299 |
| 113 | 22 | | PA | | 88-5 | 28-25-21 | D05270P | | 12 | | | | | | | D05700J | 14 | | | 050-099 |
| 113 | 22 | | PA | | 98-10 | 28-25-21 | D05270P | | 12 | | | | | | | D05700J | 14 | | | 150-199, 275-299 |
| 143 | 22 | | PA | | 106-4 | SPARE | D05700J | | 18 | | | | | | | D05042P | 2 | | | 150-154 |
| 143 | 22 | | PA | | 106-5 | SPARE | D05700J | | 18 | | | | | | | D05042P | 2 | | | 155-199 |
| 146R | 20 | | PH | | 2-8 | 26-17-11 | GD04462 | | | | D.. | 2 | | | | D07990P | 46 | | | ALL |
| 147R | 22 | | PH | | 16-10 | 26-17-11 | D10104 | | 17 | | | | | | | D07990P | 47 | | | ALL |
| 150R | 22 | | PH | | 98-10 | SPARE | D05270P | | 24 | | | | | | | D05700J | 17 | | | 150-199 |
| 150R | 22 | | PH | | 98-10 | SPARE | D05270P | | 24 | | | | | | | D05700J | 19 | | | 275-299 |
| 151 | 22 | | PA | | 15-8 | SPARE | D05270P | | 23 | | | | | | | D05042P | 31 | | | ALL |
| 152R | 20 | | PH | | 112-3 | SPARE | D05042P | | 27 | | | | | | | D06112P | 4 | | | 050-099 |
| 152R | 20 | | PH | | 133-0 | SPARE | D05042P | | 27 | | | | | | | D06112P | 4 | | | 150-199, 275-299 |
| 153 | 22 | | PA | | 23-3 | 49-61-11 | D10104 | | 12 | | | | | | | D05270P | 17 | | | ALL |
| 154 | 22 | | PA | | 16-10 | 49-61-11 | D10104 | | 13 | | | | | | | D07990P | 20 | | | ALL |
| 174 | 22 | | PA | | 11-7 | 33-16-18 | D10104 | | 3 | | | | | | | TB0031G | 10 | 2 | | ALL |
| 175 | 22 | | PA | | 11-7 | 33-16-18 | D10104 | | 4 | | | | | | | TB0031H | 13 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0610

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0614 | 286T0614 | | | FIRE DET-APU LOOP 1 & L WW,BULK & AFT CAR. (continued) | | | | | | | | | | | |
| 176 | 20 | | PA | 3-6 | 21-25-11 | D00864 | | 10 | | | GD04452 | D.. | 2 | | ALL |
| 177 | 24 | | PK | 19-4 | 21-25-11 | D00864 | | 13 | | | D05042P | | 45 | | ALL |
| 178R | 20 | | PH | 3-6 | 26-23-11 | D00864 | | 23 | | | GD04452 | D.. | 2 | | ALL |
| 179R | 20 | | PH | 48-5 | 26-23-11 | D00864 | | 15 | | | SM00099 | | 9 | | 050-099 |
| 179R | 20 | | PH | 59-3 | 26-23-11 | D00864 | | 15 | | | SM00099 | | 9 | | 150-154 |
| 179R | 20 | | PH | 59-4 | 26-23-11 | D00864 | | 15 | | | SM00099 | | 9 | | 155-199, 275-299 |
| 180R | 22 | | PH | 19-4 | 26-11-11 | D00836 | | 10 | | | D05042P | | 12 | | ALL |
| 181R | 20 | | PH | 3-4 | 26-11-11 | D00836 | | 24 | | | GD04452 | S.. | 2 | | ALL |
| 182R | 22 | | PH | 19-4 | 26-11-11 | D00836 | | 2 | | | D05042P | | 13 | | ALL |
| 185R | 22 | | PH | 19-4 | 26-11-11 | D00836 | | 25 | | | D05042P | | 36 | | ALL |
| 195R | 20 | | PH | 19-10 | 26-21-11 | D05042P | | 10 | | | SP02300 | | 9 | | ALL |
| 196R | 20 | | PH | 19-4 | 26-21-11 | D05042P | | 19 | | | D00836 | | 22 | | ALL |
| 197R | 20 | | PH | 4-6 | 26-21-11 | SP02296 | | | 9 | | D00836 | | 9 | | ALL |
| 198R | 20 | | PH | 4-6 | 26-21-11 | D00836 | | 8 | | | SP02298 | | 9 | | ALL |
| 199R | 20 | | PH | 48-6 | 26-21-11 | D10100 | | 2 | | | SM00091 | | 9 | | 050-099 |
| 199R | 20 | | PH | 59-4 | 26-21-11 | D10100 | | 2 | | | SM00091 | | 9 | | 150-199, 275-299 |
| 201B | 20 | | PB | IA | 4-9 | 33-13-18 | D10104 | | 2 | | SP05004 | | 9 | | 156-157, 166-199, 277-299 |
| 201R | 20 | | PB | IA | 0-0 | 33-13-18 | D10104 | | 1 | | SP02280 | | 9 | | 156-157, 166-199, 277-299 |
| 202B | 22 | | PR | IB | 94-4 | 31-31-22 | D05700J | | 7 | | SP03266 | | S | | 050-099 |
| 202B | 22 | | PR | AB | 51-7 | 31-31-22 | D05700J | | 7 | | SP03266 | | S | | 150-199 |
| 202B | 22 | | PR | B | 51-7 | 31-31-22 | D05700J | | 7 | | SP03266 | | S | | 275-299 |
| 202R | 22 | | PR | IB | 0-0 | 31-31-22 | D05700J | | 9 | | SP03264 | | S | | 050-099 |
| 202R | 22 | | PR | AB | 0-0 | 31-31-22 | D05700J | | 9 | | SP03264 | | S | | 150-199 |
| 202R | 22 | | PR | B | 0-0 | 31-31-22 | D05700J | | 9 | | SP03264 | | S | | 275-299 |
| 202Z | | | | IB | 0-0 | 31-31-22 | D05700J | | 8 | | SP03268 | | S | | 050-099 |
| 202Z | | | | AB | 0-0 | 31-31-22 | D05700J | | 8 | | SP03268 | | S | | 150-199 |
| 202Z | | | | B | 0-0 | 31-31-22 | D05700J | | 8 | | SP03268 | | S | | 275-299 |
| 203B | 18 | | PB | IC | 13-4 | 33-13-18 | D00864 | | 2 | DK | SP05008 | | 9 | | 156-157, 166-199, 277-299 |
| 203R | 18 | | PB | IC | 0-0 | 33-13-18 | D00864 | | 1 | DK | SP02284 | | 9 | | 156-157, 166-199, 277-299 |
| 500 | 18 | | PA | | 4-2 | 78-34-11 | D00836 | | 11 | DK | GD04474 | D.. | 2 | | ALL |
| 501 | 24 | | PK | | 19-4 | 24-22-11 | D00836 | | 21 | | D05042P | | 28 | | ALL |
| 505 | 24 | | PK | | 19-4 | 36-11-51 | D00836 | | 35 | | D05042P | | 48 | | ALL |
| 506 | 22 | | PA | | 74-6 | 29-11-11 | D00836 | | 36 | | D04546J | | 6 | | 050-099 |
| 506 | 22 | | PA | | 84-11 | 29-11-11 | D00836 | | 36 | | D04546J | | 6 | | 150-199, 275-299 |
| 507 | 22 | | PA | | 74-6 | 29-11-11 | D00836 | | 37 | | D04546J | | 5 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0610
Page 8
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0614 | 286T0614 | | | FIRE DET-APU LOOP 1 & L WW,BULK & AFT CAR. (continued) | | | | | | | | | | | | | |
| 507 | 22 | PA | | 84-11 | 29-11-11 | D00836 | | 37 | | | | | D04546J | 5 | | | 150-199, 275-299 |
| 509 | 24 | PK | | 19-4 | 78-34-11 | D00836 | | 39 | | | | | D05042P | 46 | | | ALL |
| 510 | 24 | PK | | 19-4 | 24-22-11 | D00836 | | 40 | | | | | D05042P | 29 | | | ALL |
| 512 | 20 | PA | | 19-4 | 76-11-11 | D00836 | | 6 | | | | | D05042P | 40 | | | ALL |
| 513 | 20 | PA | | 19-4 | 76-11-11 | D00836 | | 7 | | | | | D05042P | 41 | | | ALL |
| 515 | 20 | PA | | 3-4 | 31-51-33 | D00836 | | 15 | | | | | GD04452 | D.. | 2 | | ALL |
| 517 | 20 | PA | | 3-4 | 36-11-51 | D00836 | | 17 | | | | | GD04452 | D.. | 2 | | ALL |
| 518 | 22 | PA | | 19-4 | 29-11-11 | D00836 | | 18 | | | | | D05042P | 32 | | | ALL |
| 519 | 20 | PA | | 19-4 | 76-11-11 | D00836 | | 19 | | | | | D05042P | 39 | | | ALL |
| 520 | 24 | PK | | 19-4 | 78-34-11 | D00836 | | 20 | | | | | D05042P | 47 | | | ALL |
| 521 | 16 | PA | | 19-4 | 78-34-11 | D00836 | | 3 | FM | | | | D05042P | 23 | FL | | ALL |
| 522 | 16 | PA | | 19-4 | 78-34-11 | D00836 | | 12 | FM | | | | D05042P | 25 | FL | | ALL |
| 544 | 22 | PQ | VS | 19-4 | 29-11-11 | D00836 | | 13 | | | | | D05042P | 34 | | | ALL |
| 544Z | | | VS | 0-0 | 29-11-11 | D00836 | | | DED | | | | D05042P | DED | | | ALL |
| 545 | 22 | PQ | VT | 19-4 | 29-11-11 | D00836 | | 28 | | | | | D05042P | 33 | | | ALL |
| 545Z | | | VT | 0-0 | 29-11-11 | D00836 | | | DED | | | | D05042P | DED | | | ALL |
| 549 | 24 | PK | | 11-4 | 31-51-33 | D00836 | | 4 | | | | | TB0031F | C024 | 2 | | ALL |
| 551 | 22 | PA | | 11-5 | 33-16-18 | D10100 | | 3 | | | | | TB0031H | 16 | 2 | | ALL |
| 552 | 22 | PA | | 11-5 | 33-16-18 | D10100 | | 4 | | | | | TB0031G | 15 | 2 | | ALL |
| 553 | 22 | PA | | 11-4 | 33-16-18 | D00836 | | 1 | | | | | TB0031H | 18 | 2 | | ALL |
| 554 | 22 | PA | | 11-4 | 33-16-18 | D00864 | | 3 | | | | | TB0031H | 18 | 2 | | ALL |
| 555 | 22 | PA | | 11-4 | 33-16-18 | D00864 | | 4 | | | | | TB0031H | 13 | 2 | | ALL |
| 556 | 20 | PA | | 19-4 | 28-22-21 | D05042P | | 37 | | | | | D00836 | 16 | | | ALL |
| 557 | 20 | PA | | 19-4 | 28-22-21 | D05042P | | 38 | | | | | D00836 | 33 | | | ALL |
| 558 | 24 | PK | | 19-4 | 21-43-11 | D05042P | | 42 | | | | | D00864 | 6 | | | ALL |
| 559 | 24 | PK | | 19-4 | 21-43-11 | D05042P | | 43 | | | | | D00864 | 8 | | | ALL |
| 561R | 20 | PH | | 33-6 | 26-23-11 | D05270P | | 15 | | | | | SM00099 | | 9 | | 050-099 |
| 561R | 20 | PH | | 43-10 | 26-23-11 | D05270P | | 15 | | | | | SM00099 | | 9 | | 150-154 |
| 561R | 20 | PH | | 43-11 | 26-23-11 | D05270P | | 15 | | | | | SM00099 | | 9 | | 155-199, 275-299 |
| 562 | 24 | PK | | 11-4 | 31-51-33 | D00864 | | 21 | | | | | TB0031Y | C003 | BJ | | ALL |
| 563R | 20 | PH | | 33-6 | 26-21-11 | D05270P | | 14 | | | | | SM00091 | | 9 | | 050-099 |
| 563R | 20 | PH | | 43-10 | 26-21-11 | D05270P | | 14 | | | | | SM00091 | | 9 | | 150-154 |
| 563R | 20 | PH | | 43-11 | 26-21-11 | D05270P | | 14 | | | | | SM00091 | | 9 | | 155-199, 275-299 |
| 564 | 24 | PK | | 70-0 | SPARE | D05270P | | 2 | | | | | D04546J | 7 | | | 150-154 |
| 564 | 24 | PK | | 70-1 | SPARE | D05270P | | 2 | | | | | D04546J | 7 | | | 155-199, 275-299 |
| 613R | 20 | PH | | 23-0 | 26-23-12 | D05270P | | 13 | | | | | D00864 | 29 | | | 050-099 |
| 613R | 20 | PH | | 23-0 | 26-23-12 | D00864 | | 11 | | | | | D05270P | 13 | | | 150-199, 275-299 |
| 614R | 20 | PH | | 23-0 | 26-23-12 | D00864 | | 14 | | | | | D05270P | 25 | | | 155-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0610

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0614 | 286T0614 | | | FIRE DET-APU LOOP 1 & L WW,BULK & AFT CAR. (continued) | | | | | | | | | | | |
| 625R | 22 | | PH | | 23-3 | 26-17-11 | D10104 | | 15 | | D05270P | | 27 | | 050-099, 150-154, 275-299 |
| 625R | 20 | | PH | | 23-3 | 26-17-11 | D10104 | | 15 | | D05270P | | 27 | | 155-199 |
| 626R | 22 | | PH | | 23-3 | 26-17-11 | D10104 | | 16 | | D05270P | | 28 | | ALL |
| 628R | 20 | | PH | | 3-9 | 26-17-11 | D10104 | | 18 | | GD04452 | A.. | 2 | | ALL |
| 631 | 24 | | PK | | 24-6 | 25-33-11 | D05270P | | 31 | | TB0031Y | C003 | BJ | | 050-099, 150-199, 277-299 |
| 631 | 24 | | PK | | 24-6 | 21-58-16 | D05270P | | 31 | | TB0031Y | C003 | BJ | | 275-276 |
| 691 | 20 | | PQ | F1 | 14-4 | 28-22-21 | SP01750 | | | S | SP09730 | | S | | 155, 163-164, 275-278 |
| 691 | 20 | | PQ | AB | 14-4 | 28-22-21 | SP09730 | | | S | SP01750 | | S | | 280-299 |
| 691Z | | | | F1 | 0-0 | 28-22-21 | SP01750 | | DED | | SP09730 | DED | | | 155, 163-164, 275-278 |
| 691Z | | | | AB | 0-0 | 28-22-21 | SP09730 | | DED | | SP01750 | DED | | | 280-299 |
| 701R | 20 | | PH | | 7-7 | 26-23-11 | D10656 | | 3 | | GD00711 | D.. | 2 | | 050-099 |
| 701R | 20 | | PH | | 17-0 | 26-23-11 | D10656 | | 3 | | GD00711 | D.. | 2 | | 150-154 |
| 701R | 20 | | PH | | 16-9 | 26-23-11 | D10656 | | 3 | | GD00711 | D.. | 2 | | 155-199, 275-299 |
| 702R | 20 | | PH | | 9-10 | 26-23-11 | D10656 | | 2 | | SM00099 | | 9 | | 050-099 |
| 702R | 20 | | PH | | 17-6 | 26-23-11 | D10656 | | 2 | | SM00099 | | 9 | | 150-154 |
| 702R | 20 | | PH | | 6-1 | 26-23-11 | D10656 | | 2 | | SM00099 | | 9 | | 155-199, 275-299 |
| W0615 | 286T0615 | | | ADF-L,SHELF TO CONT PNL | | | | | | | | | | | |
| 001 | 18 | | PA | | 5-0 | 33-13-18 | SP02276 | | 9 | | D01629 | | 1 | DK | 050-099 |
| 001 | 18 | | PA | | 4-0 | 33-13-18 | D01629 | | 1 | DK | SP02276 | | 9 | | 150-155, 162-165, 275-276 |
| 002 | 18 | | PA | | 1-6 | 33-13-18 | GD04474 | | A.. | 2 | D01629 | | 2 | DK | 050-099, 150-155, 162-165, 275-276 |
| 003 | 22 | | PA | | 55-0 | 34-57-11 | D04575J | | 9 | | D01629 | | 9 | | 050-099 |
| 003 | 22 | | PA | | 56-0 | 34-57-11 | D04575J | | 9 | | D01629 | | 9 | | 150-199, 275-299 |
| 004 | 20 | | PA | | 10-0 | 34-57-11 | GD00094 | | A.. | 2 | D01629 | | 8 | | ALL |
| 007 | 20 | | PA | | 1-6 | 34-57-11 | GD04474 | | S.. | 2 | D01629 | | 7 | | ALL |
| 010 | 22 | | PA | | 14-0 | 34-57-11 | SP00207 | | | 9 | D01629 | | 10 | | ALL |
| 202B | 24 | | PW | IB | 55-0 | 34-57-11 | D04575J | | 11 | | D01629 | | 13 | | 050-099 |
| 202B | 24 | | PW | IB | 56-0 | 34-57-11 | D04575J | | 11 | | D01629 | | 13 | | 150-199, 275-299 |
| 202R | 24 | | PW | IB | 0-0 | 34-57-11 | D04575J | | 12 | | D01629 | | 12 | | ALL |
| 202Z | | | | IB | 0-0 | 34-57-11 | D04575J | | 10 | | D01629 | | 14 | | ALL |
| 204B | 18 | | PB | ID | 4-0 | 33-13-18 | SP05000 | | | 9 | D01629 | | 2 | DK | 156-157, 166-199, 277-299 |
| 204R | 18 | | PB | ID | 0-0 | 33-13-18 | D01629 | | 1 | DK | SP02276 | | 9 | | 156-157, 166-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0610
Page 10
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|--|----------|---------|---------|-------|------|------|---------|-------|-------------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0616 | 286T0616 | | | FWD AND AFT CARGO HANDLING, DOORS, LIGHTS & SERVICE OUTLETS | | | | | | | | | | | |
| 001 | 16 | PA | | 33-1 | 25-53-11 | D05614P | | 1 | FM | | D04926P | 1 | FL | | 050-099 |
| 001 | 16 | PA | | 34-2 | 25-53-11 | D05614P | | 1 | FM | | D04926P | 1 | FL | | 150-199, 275-299 |
| 002 | 20 | PA | | 26-5 | 25-53-11 | D05614P | | 2 | | | D05618J | 2 | | | 050-099 |
| 002 | 20 | PA | | 26-6 | 25-53-11 | D05614P | | 2 | | | D05618J | 2 | | | 150-199, 275-299 |
| 003 | 24 | PK | | 33-1 | 52-34-12 | D05614P | | 3 | | | D04926P | 3 | | | 050-099 |
| 003 | 24 | PK | | 34-2 | 52-34-12 | D05614P | | 3 | | | D04926P | 3 | | | 150-199, 275-299 |
| 004 | 24 | PK | | 26-5 | 52-34-12 | D05614P | | 4 | | | D05618J | 4 | | | 050-099 |
| 004 | 24 | PK | | 26-6 | 52-34-12 | D05614P | | 4 | | | D05618J | 4 | | | 150-199, 275-299 |
| 005 | 24 | PK | | 26-5 | 52-34-12 | D05614P | | 5 | | | D05618J | 5 | | | 050-099 |
| 005 | 24 | PK | | 26-6 | 52-34-12 | D05614P | | 5 | | | D05618J | 5 | | | 150-199, 275-299 |
| 006 | 24 | PK | | 26-5 | 52-34-12 | D05614P | | 6 | | | D05618J | 6 | | | 050-099 |
| 006 | 24 | PK | | 26-6 | 52-34-12 | D05614P | | 6 | | | D05618J | 6 | | | 150-199, 275-299 |
| 007 | 24 | PK | | 26-5 | 52-34-12 | D05614P | | 7 | | | D05618J | 7 | | | 050-099 |
| 007 | 24 | PK | | 26-6 | 52-34-12 | D05614P | | 7 | | | D05618J | 7 | | | 150-199, 275-299 |
| 008 | 24 | PK | | 26-5 | 52-34-12 | D05614P | | 8 | | | D05618J | 8 | | | 050-099 |
| 008 | 24 | PK | | 26-6 | 52-34-12 | D05614P | | 8 | | | D05618J | 8 | | | 150-199, 275-299 |
| 009 | 24 | PK | | 26-5 | 52-34-12 | D05614P | | 9 | | | D05618J | 9 | | | 050-099 |
| 009 | 24 | PK | | 26-6 | 52-34-12 | D05614P | | 9 | | | D05618J | 9 | | | 150-199, 275-299 |
| 010 | 20 | PA | | 4-11 | 25-53-13 | D05614P | | 10 | | | GD04324 | D.. | 2 | | 050-099 |
| 010 | 20 | PA | | 6-1 | 25-53-13 | D05614P | | 10 | | | GD04324 | D.. | 2 | | 150-199, 275-299 |
| 011 | 16 | PA | | 102-8 | 25-53-21 | D05616P | | 1 | FM | | D04926P | 21 | FL | | 050-099 |
| 011 | 16 | PA | | 124-2 | 25-53-21 | D05616P | | 1 | FM | | D04926P | 21 | FL | | 150-199, 275-299 |
| 012 | 20 | PA | | 96-0 | 25-53-21 | D05616P | | 2 | | | D05618J | 12 | | | 050-099 |
| 012 | 20 | PA | | 116-5 | 25-53-21 | D05616P | | 2 | | | D05618J | 12 | | | 150-199, 275-299 |
| 013 | 24 | PK | | 102-8 | 52-35-12 | D05616P | | 3 | | | D04926P | 4 | | | 050-099 |
| 013 | 24 | PK | | 124-2 | 52-35-12 | D05616P | | 3 | | | D04926P | 4 | | | 150-199, 275-299 |
| 014 | 24 | PK | | 96-0 | 52-35-12 | D05616P | | 4 | | | D05618J | 14 | | | 050-099 |
| 014 | 24 | PK | | 116-5 | 52-35-12 | D05616P | | 4 | | | D05618J | 14 | | | 150-199, 275-299 |
| 015 | 24 | PK | | 96-0 | 52-35-12 | D05616P | | 5 | | | D05618J | 15 | | | 050-099 |
| 015 | 24 | PK | | 116-5 | 52-35-12 | D05616P | | 5 | | | D05618J | 15 | | | 150-199, 275-299 |
| 016 | 24 | PK | | 96-0 | 52-35-12 | D05616P | | 6 | | | D05618J | 16 | | | 050-099 |
| 016 | 24 | PK | | 116-5 | 52-35-12 | D05616P | | 6 | | | D05618J | 16 | | | 150-199, 275-299 |
| 017 | 24 | PK | | 96-0 | 52-35-12 | D05616P | | 7 | | | D05618J | 17 | | | 050-099 |
| 017 | 24 | PK | | 116-5 | 52-35-12 | D05616P | | 7 | | | D05618J | 17 | | | 150-199, 275-299 |
| 018 | 24 | PK | | 96-0 | 52-35-12 | D05616P | | 8 | | | D05618J | 18 | | | 050-099 |
| 018 | 24 | PK | | 116-5 | 52-35-12 | D05616P | | 8 | | | D05618J | 18 | | | 150-199, 275-299 |
| 019 | 24 | PK | | 96-0 | 52-35-12 | D05616P | | 9 | | | D05618J | 19 | | | 050-099 |
| 019 | 24 | PK | | 116-5 | 52-35-12 | D05616P | | 9 | | | D05618J | 19 | | | 150-199, 275-299 |
| 020 | 20 | PA | | 8-5 | 25-53-23 | D05616P | | 10 | | | GD00300 | D.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0610

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|--------|----------|---------|------|-------|--------|---------|---------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0616 | 286T0616 | | | FWD AND AFT CARGO HANDLING, DOORS, LIGHTS & SERVICE OUTLETS (continued) | | | | | | | | | | | |
| 020 | 20 | | PA | | 8-2 | 25-53-23 | D05616P | | | | GD00300 | | D.. | 2 | 150-199, 275-299 |
| 021 | 18 | | PA | | 9-11 | 25-29-11 | D00020 | | WHT | D | GD02788 | | A.. | E | 050-099 |
| 021 | 18 | | PA | | 19-11 | 25-29-11 | D00020 | | WHT | D | GD04910 | | A.. | E | 150-199 |
| 021 | 18 | | PA | | 18-3 | 25-29-11 | D00020 | | WHT | D | GD04910 | | A.. | E | 275-299 |
| 022 | 18 | | PA | | 1-10 | 25-29-11 | D00002 | | WHT | D | GD00017 | | A.. | 2 | 050-099 |
| 022 | 18 | | PA | | 2-6 | 25-29-11 | D00002 | | WHT | D | GD00017 | | A.. | 2 | 150-199, 275-299 |
| 023 | 18 | | PA | | 1-10 | 25-29-11 | D00002 | | = GRN | D | GD00017 | | S.. | 2 | 050-099 |
| 023 | 18 | | PA | | 2-6 | 25-29-11 | D00002 | | = GRN | D | GD00017 | | S.. | 2 | 150-199, 275-299 |
| 024 | 18 | | PA | | 62-3 | 25-29-11 | D04928P | | | 14 | D00002 | | BLK | D | 050-099 |
| 024 | 18 | | PA | | 62-6 | 25-29-11 | D04928P | | | 14 | D00002 | | BLK | D | 150-199, 275-299 |
| 026 | 18 | | PA | | 164-11 | 25-29-11 | D04928P | | | 16 | D00004 | | BLK | D | 050-099 |
| 026 | 18 | | PA | | 182-11 | 25-29-11 | D04928P | | | 16 | D00004 | | BLK | D | 150-199, 275-299 |
| 027 | 18 | | PA | | 1-9 | 25-29-11 | D00004 | | WHT | D | GD04506 | | A.. | 2 | 050-099 |
| 027 | 18 | | PA | | 1-10 | 25-29-11 | D00004 | | WHT | D | GD04506 | | A.. | 2 | 150-199, 275-299 |
| 028 | 18 | | PA | | 1-9 | 25-29-11 | D00004 | | = GRN | D | GD04506 | | S.. | 2 | 050-099 |
| 028 | 18 | | PA | | 1-10 | 25-29-11 | D00004 | | = GRN | D | GD04506 | | S.. | 2 | 150-199, 275-299 |
| 029 | 18 | | PA | | 115-6 | 25-29-11 | D00020 | | | BLK | D | D04928P | | 18 | 050-099 |
| 029 | 18 | | PA | | 134-1 | 25-29-11 | D04928P | | | 18 | D00020 | | BLK | D | 150-199 |
| 029 | 18 | | PA | | 132-5 | 25-29-11 | D04928P | | | 18 | D00020 | | BLK | D | 275-299 |
| 030 | 20 | | PA | | 4-11 | 25-53-14 | D05614P | | | 15 | GD04324 | | A.. | 2 | 050-099 |
| 030 | 20 | | PA | | 6-1 | 25-53-14 | D05614P | | | 15 | GD04324 | | A.. | 2 | 150-199, 275-299 |
| 031 | 20 | | PA | | 33-1 | 52-34-11 | D04926P | | | 15 | D05614P | | 11 | | 050-099 |
| 031 | 20 | | PA | | 34-2 | 52-34-11 | D04926P | | | 15 | D05614P | | 11 | | 150-199, 275-299 |
| 032 | 20 | | PA | | 33-1 | 52-34-11 | D04926P | | | 16 | D05614P | | 12 | | 050-099 |
| 032 | 20 | | PA | | 34-2 | 52-34-11 | D04926P | | | 16 | D05614P | | 12 | | 150-199, 275-299 |
| 033 | 20 | | PA | | 33-1 | 52-34-11 | D04926P | | | 17 | D05614P | | 13 | | 050-099 |
| 033 | 20 | | PA | | 34-2 | 52-34-11 | D04926P | | | 17 | D05614P | | 13 | | 150-199, 275-299 |
| 034 | 20 | | PA | | 102-8 | 52-35-11 | D04926P | | | 18 | D05616P | | 11 | | 050-099 |
| 034 | 20 | | PA | | 124-2 | 52-35-11 | D04926P | | | 18 | D05616P | | 11 | | 150-199, 275-299 |
| 035 | 20 | | PA | | 102-8 | 52-35-11 | D04926P | | | 19 | D05616P | | 12 | | 050-099 |
| 035 | 20 | | PA | | 124-2 | 52-35-11 | D04926P | | | 19 | D05616P | | 12 | | 150-199, 275-299 |
| 036 | 20 | | PA | | 102-8 | 52-35-11 | D04926P | | | 20 | D05616P | | 13 | | 050-099 |
| 036 | 20 | | PA | | 124-2 | 52-35-11 | D04926P | | | 20 | D05616P | | 13 | | 150-199, 275-299 |
| 038 | 24 | | PK | | 31-5 | 52-34-12 | D04926P | | | 2 | D05618J | | 1 | | 050-099 |
| 038 | 24 | | PK | | 30-10 | 52-34-12 | D04926P | | | 2 | D05618J | | 1 | | 150-199, 275-299 |
| 040 | 20 | | PA | | 8-5 | 25-53-24 | D05616P | | | 15 | GD00300 | | A.. | 2 | 050-099 |
| 040 | 20 | | PA | | 8-2 | 25-53-24 | D05616P | | | 15 | GD00300 | | A.. | 2 | 150-199, 275-299 |
| 041 | 18 | | PA | | 9-11 | 25-29-11 | D00020 | | = GRN | D | GD02094 | | S.. | E | 050-099 |
| 041 | 18 | | PA | | 19-11 | 25-29-11 | D00020 | | = GRN | D | GD04914 | | S.. | E | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0610
Page 12
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|--|----------|---------|---------|-------|------|------|---------|-------|-------------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0616 | 286T0616 | | | FWD AND AFT CARGO HANDLING, DOORS, LIGHTS & SERVICE OUTLETS (continued) | | | | | | | | | | | |
| 041 | 18 | PA | | 18-3 | 25-29-11 | D00020 | = GRN | D | | | GD04914 | S.. | E | | 275-299 |
| 044 | 18 | PA | | 33-1 | 33-37-11 | D05614P | | | 14 | | D04926P | 10 | DL | | 050-099 |
| 044 | 16 | PA | | 34-2 | 33-37-11 | D05614P | | | 14 | | D04926P | 10 | FL | | 150-199, 275-299 |
| 045 | 18 | PA | | 18-4 | 33-37-11 | D04926P | | DL | 24 | | SP00784 | | 9 | | 050-099 |
| 045 | 16 | PA | | 18-9 | 33-37-11 | D04926P | | FL | 24 | | SP00784 | | 9 | | 150-199, 275-299 |
| 046 | 18 | PA | | 19-9 | 33-37-11 | D05614P | | | 16 | | SP00786 | | 9 | | 050-099 |
| 046 | 16 | PA | | 21-3 | 33-37-11 | D05614P | | | 16 | | SP00786 | | 9 | | 150-199, 275-299 |
| 047 | 20 | PA | | 26-5 | 33-37-11 | D05614P | | | 17 | | D05618J | 10 | | | 050-099 |
| 047 | 20 | PA | | 26-6 | 33-37-11 | D05614P | | | 17 | | D05618J | 10 | | | 150-199, 275-299 |
| 048 | 12 | PA | | 4-11 | 33-37-11 | D05614P | | | 18 | | GD04416 | A.. | E | | 050-099 |
| 048 | 12 | PA | | 4-6 | 33-37-11 | D05614P | | | 18 | | GD04416 | A.. | E | | 150-199, 275-299 |
| 050 | 16 | PA | | 4-11 | 33-31-61 | D05614P | | | 20 | | GD04416 | A.. | E | | 050-099 |
| 050 | 16 | PA | | 4-6 | 33-31-61 | D05614P | | | 20 | | GD04416 | A.. | E | | 150-199, 275-299 |
| 053 | 16 | PA | | 0-6 | 33-37-21 | D04926P | | FL | 27 | | SM00001 | | 9 | | ALL |
| 054 | 14 | PA | | 102-0 | 33-37-21 | D05616P | | | 14 | | SM00001 | | 9 | | 050-099 |
| 054 | 14 | PA | | 123-8 | 33-37-21 | D05616P | | | 14 | | SM00001 | | 9 | | 150-199, 275-299 |
| 057 | 20 | PA | | 96-0 | 33-37-21 | D05616P | | | 17 | | D05618J | 3 | | | 050-099 |
| 057 | 20 | PA | | 116-5 | 33-37-21 | D05616P | | | 17 | | D05618J | 3 | | | 150-199, 275-299 |
| 058 | 12 | PA | | 4-1 | 33-37-21 | D05616P | | | 18 | | GD03864 | A.. | E | | 050-099 |
| 058 | 12 | PA | | 3-10 | 33-37-21 | D05616P | | | 18 | | GD03864 | A.. | E | | 150-199, 275-299 |
| 060 | 16 | PA | | 8-5 | 33-31-61 | D05616P | | | 20 | | GD00300 | A.. | 2 | | 050-099 |
| 060 | 16 | PA | | 8-2 | 33-31-61 | D05616P | | | 20 | | GD00300 | A.. | 2 | | 150-199, 275-299 |
| 100 | 20 | PA | | 6-1 | SPARE | D04928P | | | 23 | | D04926P | 7 | | | 050-099 |
| 100 | 20 | PA | | 7-8 | SPARE | D04928P | | | 23 | | D04926P | 7 | | | 150-199, 275-299 |
| 101 | 20 | PA | | 26-5 | SPARE | D05618J | | | 23 | | D05614P | 23 | | | 050-099 |
| 101 | 20 | PA | | 26-6 | SPARE | D05618J | | | 23 | | D05614P | 23 | | | 150-199, 275-299 |
| 801 | 20 | PA | | 35-3 | SPARE | D04928P | | | 25 | | D05614P | 25 | | | 050-099 |
| 801 | 20 | PA | | 36-3 | SPARE | D04928P | | | 25 | | D05614P | 25 | | | 150-199, 275-299 |
| 802 | 20 | PA | | 96-0 | SPARE | D05618J | | | 21 | | D05616P | 21 | | | 050-099 |
| 802 | 20 | PA | | 116-5 | SPARE | D05618J | | | 21 | | D05616P | 21 | | | 150-199, 275-299 |
| A-A | | | | 0-0 | 33-37-11 | S00403 | | | 1 | | SP00784 | | 9 | | ALL |
| A-B | | | | 0-0 | 33-37-11 | S00403 | | | 2 | | SP00786 | | 9 | | ALL |
| A-C | | | | 0-0 | 33-37-11 | S00403 | | | 3 | | S00403 | CAP | Y | | ALL |
| A-D | | | | 0-0 | 33-37-11 | S00403 | | | 4 | | S00403 | CAP | Y | | ALL |
| W0617 | 286T0617 | | | ADF-R, SHELF TO CONT PANEL | | | | | | | | | | | |
| 003 | 22 | PQ | AC | 55-0 | 34-57-21 | D01631 | | | 9 | | D04577J | 9 | | | 050-099 |
| 003 | 22 | PQ | AC | 54-0 | 34-57-21 | D01631 | | | 9 | | D04577J | 9 | | | 150-199, 275-299 |
| 003Z | | | AC | 0-0 | 34-57-21 | D01631 | | DED | | | D04577J | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0610

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | To | | | | |
|--------------|-----------------|-------------|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0617 | 286T0617 | | | ADF-R,SHELF TO CONT PANEL (continued) | | | | | | | | | | | |
| 004 | 20 | PQ | AD | | 10-0 | 34-57-21 | D01631 | | 8 | | GD02466 | A.. | 2 | | ALL |
| 004Z | | | AD | | 0-0 | 34-57-21 | D01631 | DED | | | GD02466 | DED | | | ALL |
| 007 | 20 | PA | | | 1-6 | 34-57-21 | D01631 | | 7 | | GD04474 | S.. | 2 | | ALL |
| 010 | 22 | PQ | AJ | | 13-0 | 34-57-21 | D01631 | | 10 | | SP00371 | | 9 | | ALL |
| 010Z | | | AJ | | 0-0 | 34-57-21 | D01631 | DED | | | SP00371 | DED | | | ALL |
| 202B | 24 | PW | IB | | 55-0 | 34-57-21 | D01631 | | 13 | | D04577J | | 11 | | 050-099 |
| 202B | 24 | PW | IB | | 54-0 | 34-57-21 | D01631 | | 13 | | D04577J | | 11 | | 150-199, 275-299 |
| 202R | 24 | PW | IB | | 0-0 | 34-57-21 | D01631 | | 12 | | D04577J | | 12 | | ALL |
| 202Z | | | IB | | 0-0 | 34-57-21 | D01631 | | 14 | | D04577J | | 10 | | ALL |
| W0619 | 286T0619 | | | YAW DAMPER L,SHELF TO TAIL DISC | | | | | | | | | | | |
| 001 | 24 | PK | | | 126-9 | 31-51-41 | D04565J | | 6 | | D04783P | | 1 | | 050-099 |
| 001 | 24 | PK | | | 148-4 | 31-51-41 | D04565J | | 6 | | D04783P | | 1 | | 150-199, 275-299 |
| 203B | 22 | PB | IC | | 126-9 | 27-58-21 | D04565J | | 1 | | D04783P | | 11 | | 050-099 |
| 203B | 22 | PB | IC | | 148-4 | 27-58-21 | D04565J | | 1 | | D04783P | | 11 | | 150-199, 275-299 |
| 203R | 22 | PB | IC | | 0-0 | 27-58-21 | D04565J | | 2 | | D04783P | | 12 | | ALL |
| 302B | 24 | PM | MB | | 126-9 | 27-58-21 | D04565J | | 3 | | D04783P | | 13 | | 050-099 |
| 302B | 24 | PM | MB | | 148-4 | 27-58-21 | D04565J | | 3 | | D04783P | | 13 | | 150-199, 275-299 |
| 302R | 24 | PM | MB | | 0-0 | 27-58-21 | D04565J | | 4 | | D04783P | | 14 | | ALL |
| 302Y | 24 | PM | MB | | 0-0 | 27-58-21 | D04565J | | 5 | | D04783P | | 15 | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|----------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0620 | 286T0620 | | | R EDHP SOV, HYD IND | | | | | | | | | | | | | |
| 001 | 24 | | PK | 15-4 | 28-22-11 | D04286P | | 1 | | | | | D04284P | 1 | | | ALL |
| 002 | 16 | | PA | 25-1 | 28-22-11 | D04286P | | 15 | | | | | D05800P | 4 | | | ALL |
| 003 | 16 | | PA | 25-1 | 28-22-11 | D04286P | | 19 | | | | | D05800P | 7 | | | ALL |
| 004 | 16 | | PA | 25-1 | 28-22-11 | D04286P | | 23 | | | | | D05800P | 10 | | | ALL |
| 005 | 20 | | UA | 10-0 | 78-34-21 | D04284P | | | | | FA | | GD00754 | S.. | 2 | | ALL |
| 010 | 22 | | PA | 15-4 | SPARE | D04286P | | 10 | | | | | D04284P | 10 | | | 150-154, 275 |
| 012 | 24 | | PK | 15-4 | 28-22-12 | D04286P | | 12 | | | | | D04284P | 12 | | | ALL |
| 014 | 18 | | PA | 15-4 | 38-32-14 | D04286P | | 2 | DL | | | | D04284P | 5 | DL | | ALL |
| 018 | 24 | | PK | 15-4 | 28-22-12 | D04286P | | 28 | | | | | D04284P | 14 | | | 050-099, 155-199, 276-299 |
| 019 | 22 | | PA | 15-4 | 28-31-11 | D04286P | | 5 | | | | | D04284P | 6 | | | 050-099, 155-199, 276-299 |
| 021 | 24 | | PK | 15-4 | 38-15-11 | D04286P | | 16 | | | | | D04284P | 20 | | | ALL |
| 023 | 20 | | PA | 15-4 | 33-42-11 | D04286P | | 17 | | | | | D04284P | 17 | | | ALL |
| 024 | 20 | | PA | 15-4 | 28-31-11 | D04286P | | 7 | | | | | D04284P | 7 | | | 050-099, 155-199, 276-299 |
| 025 | 20 | | PA | 15-4 | 28-31-11 | D04286P | | 9 | | | | | D04284P | 8 | | | 050-099, 155-199, 276-299 |
| 026 | 24 | | PK | 15-4 | 36-21-11 | D04286P | | 26 | | | | | D04284P | 26 | | | ALL |
| 027 | 22 | | PA | 15-4 | 28-31-11 | D04286P | | 10 | | | | | D04284P | 3 | | | 050-099, 155-199, 276-299 |
| 028 | 22 | | PA | 15-4 | 28-31-12 | D04286P | | 11 | | | | | D04284P | 9 | | | 050-099, 155-199, 276-299 |
| 029 | 20 | | PA | 15-4 | 28-31-12 | D04286P | | 18 | | | | | D04284P | 10 | | | 050-099, 155-199, 276-299 |
| 031 | 24 | | PK | 15-4 | SPARE | D04286P | | 21 | | | | | D04284P | 2 | | | ALL |
| 040 | 18 | | PA | 15-4 | 38-32-11 | D04284P | | 21 | | | | | D04286P | 8 | DL | | 050-099, 150-199, 277-299 |
| 040 | 18 | | PA | 15-4 | SPARE | D04284P | | 21 | | | | | D04286P | 8 | DL | | 275-276 |
| 041 | 22 | | PA | 15-4 | SPARE | D04284P | | 19 | | | | | D04286P | 20 | | | 150-154, 275 |
| 047 | 20 | | PA | 15-4 | 28-31-12 | D04286P | | 20 | | | | | D04284P | 11 | | | 050-099, 155-199, 276-299 |
| 048 | 22 | | PA | 15-4 | 28-31-21 | D04286P | | 6 | | | | | D04284P | 4 | | | 050-099, 155-199, 276-299 |
| 049 | 22 | | PA | 15-4 | 28-42-12 | D04286P | | 22 | | | | | D04284P | 15 | | | 050-099, 155-199, 276-299 |
| 050 | 20 | | PA | 15-4 | SPARE | D04286P | | 5 | | | | | D04284P | 3 | | | 150-154, 275 |
| 051 | 24 | | PK | 25-1 | 21-51-13 | D04286P | | 13 | | | | | D05800P | 2 | | | ALL |
| 052 | 24 | | PK | 25-1 | 21-51-13 | D04286P | | 14 | | | | | D05800P | 3 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0620

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0620 | 286T0620 | | | R EDHP SOV, HYD IND (continued) | | | | | | | | | | | |
| 053 | 22 | | PA | | 15-4 | 28-42-13 | D04286P | 24 | | | D04284P | 13 | | | 050-099, 155-199, 276-299 |
| 054 | 22 | | PA | | 15-4 | 28-31-12 | D04286P | 25 | | | D04284P | 16 | | | 050, 155-199, 277-299 |
| 054 | 22 | | PA | | 20-0 | 28-31-12 | D04284P | 16 | | | D04286P | 25 | | | 051-099 |
| 073 | 20 | | PQ | CW | 20-0 | 78-34-21 | D04284P | 31 | | | D05800P | 5 | | | ALL |
| 073Z | | | | CW | 0-0 | 78-34-21 | D04284P | | | FA | D05800P | 12 | | | ALL |
| 074 | 20 | | PA | | 20-0 | 78-34-21 | D04284P | 30 | | | D05800P | 6 | | | ALL |
| 075 | 20 | | PA | | 20-0 | 78-34-21 | D04284P | 29 | | | D05800P | 8 | | | ALL |
| 201B | 24 | | PL | AA | 15-4 | 36-21-11 | D04286P | 3 | | | D04284P | 28 | | | ALL |
| 201R | 24 | | PL | AA | 0-0 | 36-21-11 | D04286P | 4 | | | D04284P | 27 | | | ALL |
| 801 | 20 | | PA | | 25-1 | SPARE | D04286P | 28 | | | D05800P | 1 | | | 150-154, 275 |
| FRA | | | | | 0-0 | 78-34-21 | D04284P | | | FA | D04284P | 32 | | | ALL |
| W0622 | 286T0622 | | | WSHLD HTR, | | | | | | | | | | | |
| 001 | 24 | | PK | | 31-0 | 30-41-11 | D05064P | 1 | | | D05344J | 16 | | | ALL |
| 002 | 24 | | PK | | 31-0 | 30-41-11 | D05064P | 2 | | | D05344J | 10 | | | ALL |
| 004 | 20 | | PA | | 15-0 | 30-41-11 | D04288P | 12 | | | D05344J | 4 | | | ALL |
| 005 | 20 | | PA | | 15-0 | 30-41-11 | D04288P | 13 | | | D05344J | 5 | | | ALL |
| 006 | 24 | | PK | | 31-0 | 30-41-11 | D05064P | 6 | | | D05344J | 6 | | | ALL |
| 007 | 24 | | PK | | 31-0 | 30-41-11 | D05064P | 4 | | | D05344J | 7 | | | ALL |
| 008 | 22 | | PA | | 31-0 | 30-41-11 | D05064P | 8 | | | D05344J | 8 | | | ALL |
| 009 | 22 | | PA | | 31-0 | 30-41-11 | D05064P | 9 | | | D05344J | 9 | | | ALL |
| 010 | 20 | | PA | | 34-0 | 30-41-11 | D04292J | 14 | | | D05870J | 1 | | | ALL |
| 011 | 22 | | PA | | 51-0 | 25-11-11 | D05064P | 11 | | | D00910 | 1 | | | ALL |
| 012 | 22 | | PA | | 51-0 | 25-11-11 | D05064P | 12 | | | D00910 | 2 | | | ALL |
| 013 | 22 | | PA | | 51-0 | 25-11-11 | D05064P | 13 | | | D00910 | 3 | | | ALL |
| 014 | 20 | | PA | | 4-0 | 25-11-11 | GD00027 | S.. | 2 | | D00910 | 5 | | | ALL |
| 015 | 22 | | PA | | 46-0 | 30-31-11 | D05064P | 5 | | | D01010 | A | | | ALL |
| 017 | 22 | | PA | | 46-0 | 30-31-11 | D05064P | 7 | | | D01010 | B | | | ALL |
| 020 | 20 | | PA | | 5-0 | 30-41-11 | D05870J | 2 | | | GD04430 | A.. | 2 | | ALL |
| 021 | 20 | | PA | | 30-0 | 30-41-11 | D04292J | 21 | | | SM00007 | 9 | | | ALL |
| 022 | 20 | | PA | | 5-0 | 30-41-11 | SM00008 | | 9 | | GD04510 | A.. | 2 | | ALL |
| 030 | 18 | | PA | | 39-0 | 38-32-11 | D05064P | 23 | | | D05456P | 9 | | | 156-157, 166-199, 277-299 |
| 031 | 18 | | PA | | 39-0 | 38-32-11 | D05064P | 24 | DL | | D05456P | 10 | | | 156-157, 166-199, 277-299 |
| 033 | 24 | | PK | | 21-0 | 21-53-11 | D05064P | 25 | | | D08040J | 1 | | | ALL |
| 034 | 24 | | PK | | 32-0 | 21-53-11 | D04288P | 2 | | | D08040J | 2 | | | ALL |
| 035 | 24 | | PK | | 32-0 | 21-53-11 | D04288P | 3 | | | D08040J | 3 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0620
 Page 2
 Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|-------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0622 | 286T0622 | | | WSHLD HTR, (continued) | | | | | | | | | | | | | |
| 036 | 24 | | PK | 32-0 | 21-53-11 | D04288P | | 4 | | | | | D08040J | 4 | | | ALL |
| 037 | 24 | | PK | 32-0 | 21-53-11 | D04288P | | 5 | | | | | D08040J | 5 | | | ALL |
| 038 | 24 | | PK | 32-0 | 21-53-11 | D04288P | | 6 | | | | | D08040J | 6 | | | ALL |
| 039 | 24 | | PK | 32-0 | 21-53-11 | D04288P | | 7 | | | | | D08040J | 7 | | | ALL |
| 041 | 24 | | PK | 32-0 | 21-53-11 | D08040J | | 9 | | | | | D04288P | 24 | | | ALL |
| 042 | 22 | | PA | 39-0 | SPARE | D05064P | | 26 | | | | | D04288P | 9 | | | ALL |
| 044 | 24 | | PK | 39-0 | 21-43-11 | D05064P | | 28 | | | | | D04288P | 11 | | | ALL |
| 047 | 24 | | PK | 39-0 | 21-44-11 | D05064P | | 31 | | | | | D04288P | 18 | | | ALL |
| 048 | 24 | | PK | 39-0 | 21-43-11 | D05064P | | 3 | | | | | D04288P | 8 | | | ALL |
| 049 | 20 | | PA | 39-0 | 21-31-11 | D05064P | | 33 | | | | | D04288P | 28 | | | ALL |
| 054 | 22 | | PA | 39-0 | SPARE | D05456P | | 2 | | | | | D05064P | 20 | | | ALL |
| 055 | 18 | | PA | 39-0 | 38-32-11 | D05456P | | 3 | | | | | D05064P | 21 | | | ALL |
| 056 | 24 | | PK | 21-0 | 21-52-41 | D05064P | | 18 | | | | | D08040J | 8 | | | ALL |
| 060 | 12 | | PA | 3-0 | 30-41-11 | D04292J | | 8 | | | | | GD00520 | S.. | E | | ALL |
| 061 | 12 | | PA | 2-0 | 30-41-11 | D04292J | | 10 | | | | | GD00522 | A.. | E | | ALL |
| 069 | 22 | | PA | 21-0 | SPARE | D05064P | | 34 | | | | | D08040J | 10 | | | ALL |
| 070 | 22 | | PA | 33-0 | SPARE | D05456P | | 5 | | | | | D08040J | 11 | | | ALL |
| 071 | 20 | | PA | 39-0 | SPARE | D05064P | | 35 | | | | | D05456P | 4 | | | ALL |
| 072 | 20 | | PA | 31-0 | SPARE | D05064P | | 36 | | | | | D05344J | 19 | | | ALL |
| 201B | 24 | | PW | A | 26-0 | 30-41-11 | TB0322F | A005 | 2 | | | | SM00015 | | 9 | | 050-099, 155-199, 277-299 |
| 201B | 24 | | PW | A | 28-0 | 30-41-11 | TB0322F | A005 | 2 | | | | SM00015 | | 9 | | 150-154, 275-276 |
| 201R | 24 | | PW | A | 0-0 | 30-41-11 | TB0322F | C005 | 2 | | | | SM00016 | | 9 | | ALL |
| 201Z | | | | A | 0-0 | 30-41-11 | TB0322F | | | | | FA | SM00015 | DED | | | ALL |
| 202B | 24 | | PW | B | 26-0 | 30-41-11 | TB0322F | A006 | 2 | | | | SM00017 | | 9 | | 050-099, 155-199, 277-299 |
| 202B | 24 | | PW | B | 28-0 | 30-41-11 | TB0322F | A006 | 2 | | | | SM00017 | | 9 | | 150-154, 275-276 |
| 202R | 24 | | PW | B | 0-0 | 30-41-11 | TB0322F | C006 | 2 | | | | SM00018 | | 9 | | ALL |
| 202Z | | | | B | 0-0 | 30-41-11 | TB0322F | | | | | FA | SM00017 | DED | | | ALL |
| 203B | 24 | | PW | C | 38-0 | 30-41-11 | TB0322F | A003 | 2 | | | | D05870J | 3 | | | 050-099, 155-199, 277-299 |
| 203B | 24 | | PW | C | 34-0 | 30-41-11 | TB0322F | A003 | 2 | | | | D05870J | 3 | | | 150-154, 275-276 |
| 203R | 24 | | PW | C | 0-0 | 30-41-11 | TB0322F | C003 | 2 | | | | D05870J | 4 | | | ALL |
| 203Z | | | | C | 0-0 | 30-41-11 | TB0322F | | | | | FB | D05870J | DED | | | ALL |
| 204B | 24 | | PW | D | 38-0 | 30-41-11 | TB0322F | A004 | 2 | | | | D05870J | 5 | | | 050-099, 155-199, 277-299 |
| 204B | 24 | | PW | D | 34-0 | 30-41-11 | TB0322F | A004 | 2 | | | | D05870J | 5 | | | 150-154, 275-276 |
| 204R | 24 | | PW | D | 0-0 | 30-41-11 | TB0322F | C004 | 2 | | | | D05870J | 6 | | | ALL |
| 204Z | | | | D | 0-0 | 30-41-11 | TB0322F | | | | | FB | D05870J | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0620

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0622 | 286T0622 | | | WSHLD HTR, (continued) | | | | | | | | | | | |
| 205B | 24 | PW | E | 36-0 | 30-41-11 | TB0322F | A001 | 2 | | SM00009 | | 9 | | 050-099, 155-199, 277-299 | |
| 205B | 24 | PW | E | 31-0 | 30-41-11 | TB0322F | A001 | 2 | | SM00009 | | 9 | | 150-154, 275-276 | |
| 205R | 24 | PW | E | 0-0 | 30-41-11 | TB0322F | C001 | 2 | | SM00010 | | 9 | | ALL | |
| 205Z | | | E | 0-0 | 30-41-11 | TB0322F | | | FC | SM00009 | | DED | | ALL | |
| 206B | 24 | PW | F | 36-0 | 30-41-11 | TB0322F | A002 | 2 | | SM00011 | | 9 | | 050-099, 155-199, 277-299 | |
| 206B | 24 | PW | F | 31-0 | 30-41-11 | TB0322F | A002 | 2 | | SM00011 | | 9 | | 150-154, 275-276 | |
| 206R | 24 | PW | F | 0-0 | 30-41-11 | TB0322F | C002 | 2 | | SM00012 | | 9 | | ALL | |
| 206Z | | | F | 0-0 | 30-41-11 | TB0322F | | | FC | SM00011 | | DED | | ALL | |
| 207B | 24 | PW | G | 15-0 | 21-31-11 | D05344J | | 12 | | D04288P | | 21 | | ALL | |
| 207R | 24 | PW | G | 0-0 | 21-31-11 | D05344J | | 11 | | D04288P | | 20 | | ALL | |
| 207Z | | | G | 0-0 | 21-31-11 | D05344J | | 13 | | D04288P | | 22 | | ALL | |
| 209B | 12 | PB | J | 28-0 | 30-41-11 | D04292J | | 4 | | SM00013 | | 9 | | ALL | |
| 209R | 12 | PB | J | 0-0 | 30-41-11 | D04292J | | 6 | | SM00014 | | 9 | | ALL | |
| 210B | 12 | PB | K | 15-0 | 30-41-11 | D04288P | | 19 | | D04292J | | 1 | | ALL | |
| 210R | 12 | PB | K | 0-0 | 30-41-11 | D04288P | | 23 | | D04292J | | 2 | | ALL | |
| 211B | 20 | PB | H | 15-0 | 21-31-11 | D05344J | | 14 | | D04288P | | 25 | | ALL | |
| 211R | 20 | PB | H | 0-0 | 21-31-11 | D05344J | | 15 | | D04288P | | 26 | | ALL | |
| 212B | 24 | PW | I | 12-0 | 30-41-11 | TB0322F | A002 | 2 | | D04292J | | 23 | | ALL | |
| 212R | 24 | PW | I | 0-0 | 30-41-11 | TB0322F | C002 | 2 | | D04292J | | 24 | | ALL | |
| 212Z | | | I | 0-0 | 30-41-11 | TB0322F | | | FC | D04292J | | 7 | | ALL | |
| 213B | 24 | PW | L | 12-0 | 30-41-11 | TB0322F | A004 | 2 | | D04292J | | 19 | | ALL | |
| 213R | 24 | PW | L | 0-0 | 30-41-11 | TB0322F | C004 | 2 | | D04292J | | 20 | | ALL | |
| 213Z | | | L | 0-0 | 30-41-11 | TB0322F | | | FB | D04292J | | 5 | | ALL | |
| 214B | 24 | PW | M | 12-0 | 30-41-11 | TB0322F | A006 | 2 | | D04292J | | 15 | | ALL | |
| 214R | 24 | PW | M | 0-0 | 30-41-11 | TB0322F | C006 | 2 | | D04292J | | 16 | | ALL | |
| 214Z | | | M | 0-0 | 30-41-11 | TB0322F | | | FA | D04292J | | 3 | | ALL | |
| 61K | 18 | PA | | 39-0 | 38-32-14 | D05064P | | 14 | DL | D05456P | | 6 | | ALL | |
| A-A | | | | 0-0 | 30-41-11 | SM00013 | | 9 | | D01656 | | =1 | | ALL | |
| A-B | | | | 0-0 | 30-41-11 | SM00013 | | 9 | | D01658 | | =1 | | ALL | |
| A-C | | | | 0-0 | 30-41-11 | SM00014 | | 9 | | D01660 | | =1 | | ALL | |
| A-D | | | | 0-0 | 30-41-11 | SM00015 | | 9 | | D01898 | | A | | ALL | |
| A-E | | | | 0-0 | 30-41-11 | SM00016 | | 9 | | D01898 | | B | | ALL | |
| A-F | | | | 0-0 | 30-41-11 | SM00017 | | 9 | | D01900 | | A | | ALL | |
| A-G | | | | 0-0 | 30-41-11 | SM00018 | | 9 | | D01900 | | B | | ALL | |
| A-P | | | | 0-0 | 30-41-11 | SM00007 | | 9 | | D01662 | | =1 | | ALL | |
| A-R | | | | 0-0 | 30-41-11 | SM00008 | | 9 | | D00892 | | =1 | | ALL | |
| A-S | | | | 0-0 | 30-41-11 | SM00009 | | 9 | | D01908 | | A | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0620
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0622 | 286T0622 | | | WSHLD HTR, (continued) | | | | | | | | | | | | |
| A-T | | | | 0-0 | 30-41-11 | SM00010 | | | | 9 | | | D01908 | B | | ALL |
| A-U | | | | 0-0 | 30-41-11 | SM00011 | | | | 9 | | | D01910 | A | | ALL |
| A-V | | | | 0-0 | 30-41-11 | SM00012 | | | | 9 | | | D01910 | B | | ALL |
| W0623 | 286T0623 | | | AUD-ADF L SHELF TO SHELF | | | | | | | | | | | | |
| 001 | 24 | PV | AA | 42-0 | 23-51-13 | D04579J | | | | 1 | | | D04581J | 1 | | 050-099 |
| 001 | 24 | PV | AA | 43-0 | 23-51-13 | D04579J | | | | 1 | | | D04581J | 1 | | 150-199, 275-299 |
| 001Z | | | AA | 0-0 | 23-51-13 | D04579J | | | | 2 | | | D04581J | 2 | | ALL |
| 002 | 22 | PA | | 42-0 | SPARE | D04579J | | | | 3 | | | D04581J | 3 | | 050-099 |
| 002 | 22 | PA | | 43-0 | SPARE | D04579J | | | | 3 | | | D04581J | 3 | | 150-199, 275-299 |
| 003 | 24 | PV | AC | 42-0 | 23-51-13 | D04579J | | | | 4 | | | D04581J | 4 | | 050-099 |
| 003 | 24 | PV | AC | 43-0 | 23-51-13 | D04579J | | | | 4 | | | D04581J | 4 | | 150-199, 275-299 |
| 003Z | | | AC | 0-0 | 23-51-13 | D04579J | | | | 5 | | | D04581J | 5 | | ALL |
| 201B | 24 | PW | IA | 42-0 | 31-35-13 | D04579J | | | | 7 | | | D04581J | 7 | | 050-099 |
| 201B | 24 | PW | IA | 43-0 | 31-35-13 | D04579J | | | | 7 | | | D04581J | 7 | | 150-199, 275-299 |
| 201R | 24 | PW | IA | 0-0 | 31-35-13 | D04579J | | | | 6 | | | D04581J | 6 | | ALL |
| 201Z | | | IA | 0-0 | 31-35-13 | D04579J | | | | 8 | | | D04581J | 8 | | ALL |
| 202B | 24 | PW | IB | 43-0 | SPARE | D04579J | | | | 10 | | | D04581J | 10 | | 150-199 |
| 202R | 24 | PW | IB | 0-0 | SPARE | D04579J | | | | 9 | | | D04581J | 9 | | 150-199 |
| 202Z | | | IB | 0-0 | SPARE | D04579J | | | | 11 | | | D04581J | 11 | | 150-199 |
| W0624 | 286T0624 | | | WSHLD HTR, | | | | | | | | | | | | |
| 001 | 22 | PA | | 15-0 | 25-11-21 | D05062P | | | | 1 | | | D00912 | 1 | | 050-099 |
| 001 | 22 | PA | | 13-4 | 25-11-21 | D05062P | | | | 1 | | | D00912 | 1 | | 150-199, 275-299 |
| 002 | 22 | PA | | 15-0 | 25-11-21 | D05062P | | | | 2 | | | D00912 | 2 | | 050-099 |
| 002 | 22 | PA | | 13-4 | 25-11-21 | D05062P | | | | 2 | | | D00912 | 2 | | 150-199, 275-299 |
| 003 | 22 | PA | | 15-0 | 25-11-21 | D05062P | | | | 3 | | | D00912 | 3 | | 050-099 |
| 003 | 22 | PA | | 13-4 | 25-11-21 | D05062P | | | | 3 | | | D00912 | 3 | | 150-199, 275-299 |
| 004 | 20 | PA | | 4-0 | 25-11-21 | GD04510 | | | S.. | 2 | | | D00912 | 5 | | 050-099 |
| 004 | 20 | PA | | 4-3 | 25-11-21 | GD04510 | | | S.. | 2 | | | D00912 | 5 | | 150-199, 275-299 |
| 005 | 24 | PK | | 23-0 | 30-41-12 | D05356P | | | | 5 | | | D05932J | 5 | | 050-099 |
| 005 | 24 | PK | | 22-6 | 30-41-12 | D05356P | | | | 5 | | | D05932J | 5 | | 150-199, 275-299 |
| 006 | 22 | PA | | 23-0 | 30-41-12 | D05356P | | | | 6 | | | D05932J | 6 | | 050-099 |
| 006 | 22 | PA | | 22-6 | 30-41-12 | D05356P | | | | 6 | | | D05932J | 6 | | 150-199, 275-299 |
| 007 | 24 | PK | | 23-0 | 30-41-12 | D05356P | | | | 7 | | | D05932J | 7 | | 050-099 |
| 007 | 24 | PK | | 22-6 | 30-41-12 | D05356P | | | | 7 | | | D05932J | 7 | | 150-199, 275-299 |
| 009 | 22 | PA | | 10-0 | 30-31-21 | D05356P | | | | 9 | | | D00574 | A | | 050-099 |
| 009 | 22 | PA | | 9-10 | 30-31-21 | D05356P | | | | 9 | | | D00574 | A | | 150-199, 275-299 |
| 010 | 22 | PA | | 24-0 | 30-31-21 | D05744P | | | | 10 | | | D00574 | B | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0620

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|---------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0624 | 286T0624 | | | WSHLD HTR, (continued) | | | | | | | | | | | |
| 010 | 22 | | PA | | 23-6 | 30-31-21 | D05744P | | | | D00574 | | B | | 150-199, 275-299 |
| 011 | 20 | | PA | | 35-0 | 30-41-12 | D04294J | | | | SM00001 | | 9 | | 050-099 |
| 011 | 20 | | PA | | 33-2 | 30-41-12 | D04294J | | | | SM00001 | | 9 | | 150-199, 275-299 |
| 012 | 24 | | PK | | 23-0 | 30-41-12 | D05356P | | | | D05932J | | 2 | | 050-099 |
| 012 | 24 | | PK | | 22-6 | 30-41-12 | D05356P | | | | D05932J | | 2 | | 150-199, 275-299 |
| 013 | 24 | | PK | | 23-0 | 30-41-12 | D05356P | | | | D05932J | | 3 | | 050-099 |
| 013 | 24 | | PK | | 22-6 | 30-41-12 | D05356P | | | | D05932J | | 3 | | 150-199, 275-299 |
| 014 | 22 | | PA | | 23-0 | 30-41-12 | D05356P | | | | D05932J | | 4 | | 050-099 |
| 014 | 22 | | PA | | 22-6 | 30-41-12 | D05356P | | | | D05932J | | 4 | | 150-199, 275-299 |
| 015 | 20 | | PA | | 12-0 | 30-41-12 | SM00002 | | | 9 | GD00434 | | A.. | 2 | 050-099 |
| 015 | 20 | | PA | | 8-11 | 30-41-12 | SM00002 | | | 9 | GD00434 | | A.. | 2 | 150-199, 275-299 |
| 016 | 22 | | PA | | 24-0 | 30-31-23 | D05744P | | | 16 | D01012 | | B | | 050-099 |
| 016 | 22 | | PA | | 23-5 | 30-31-23 | D05744P | | | 16 | D01012 | | B | | 150-199, 275-299 |
| 019 | 20 | | PA | | 47-0 | 30-41-12 | SM00007 | | | 9 | D04294J | | 21 | | 050-099 |
| 019 | 20 | | PA | | 46-8 | 30-41-12 | SM00007 | | | 9 | D04294J | | 21 | | 150-199, 275-299 |
| 020 | 20 | | PA | | 7-0 | 30-41-12 | GD00027 | | | A.. | 2 | SM00008 | | 9 | 050-099 |
| 020 | 20 | | PA | | 4-8 | 30-41-12 | GD00027 | | | A.. | 2 | SM00008 | | 9 | 150-199, 275-299 |
| 024 | 24 | | PK | | 16-0 | 21-43-11 | D04296P | | | 17 | D05192P | | 3 | | 050-099 |
| 024 | 24 | | PK | | 16-1 | 21-43-11 | D04296P | | | 17 | D05192P | | 3 | | 150-199, 275-299 |
| 025 | 22 | | PA | | 41-0 | 30-31-23 | D05356P | | | 25 | D01012 | | A | | 050-099 |
| 025 | 22 | | PA | | 40-10 | 30-31-23 | D05356P | | | 25 | D01012 | | A | | 150-199, 275-299 |
| 026 | 24 | | PK | | 29-0 | 21-53-12 | D05062P | | | 20 | D05192P | | 1 | | 050-099 |
| 026 | 24 | | PK | | 28-4 | 21-53-12 | D05062P | | | 20 | D05192P | | 1 | | 150-199, 275-299 |
| 027 | 24 | | PK | | 16-0 | 21-43-11 | D04296P | | | 8 | D05192P | | 2 | | 050-099 |
| 027 | 24 | | PK | | 16-1 | 21-43-11 | D04296P | | | 8 | D05192P | | 2 | | 150-199, 275-299 |
| 029 | 24 | | PK | | 12-0 | 21-44-21 | D04296P | | | 18 | D05744P | | 34 | | 050-099 |
| 029 | 24 | | PK | | 11-6 | 21-44-21 | D04296P | | | 18 | D05744P | | 34 | | 150-199, 275-299 |
| 033 | 24 | | PK | | 17-0 | 21-53-21 | D05062P | | | 5 | D08052J | | 1 | | 050-099 |
| 033 | 24 | | PK | | 16-7 | 21-53-21 | D05062P | | | 5 | D08052J | | 1 | | 150-199, 275-299 |
| 034 | 24 | | PK | | 11-0 | 21-53-21 | D05744P | | | 26 | D08052J | | 2 | | 050-099 |
| 034 | 24 | | PK | | 10-7 | 21-53-21 | D05744P | | | 26 | D08052J | | 2 | | 150-199, 275-299 |
| 035 | 24 | | PK | | 11-0 | 21-53-21 | D05744P | | | 25 | D08052J | | 3 | | 050-099 |
| 035 | 24 | | PK | | 10-7 | 21-53-21 | D05744P | | | 25 | D08052J | | 3 | | 150-199, 275-299 |
| 036 | 24 | | PK | | 11-0 | 21-53-21 | D05744P | | | 30 | D08052J | | 4 | | 050-099 |
| 036 | 24 | | PK | | 10-7 | 21-53-21 | D05744P | | | 30 | D08052J | | 4 | | 150-199, 275-299 |
| 037 | 24 | | PK | | 11-0 | 21-53-21 | D05744P | | | 29 | D08052J | | 5 | | 050-099 |
| 037 | 24 | | PK | | 10-7 | 21-53-21 | D05744P | | | 29 | D08052J | | 5 | | 150-199, 275-299 |
| 038 | 24 | | PK | | 11-0 | 21-53-21 | D05744P | | | 28 | D08052J | | 6 | | 050-099 |
| 038 | 24 | | PK | | 10-7 | 21-53-21 | D05744P | | | 28 | D08052J | | 6 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0620

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|---------|-------|-------|------|--------|-------|------|---------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0624 | 286T0624 | | | WSHLD HTR, (continued) | | | | | | | | | | | | |
| 039 | 24 | | PK | 11-0 | 21-53-21 | D05744P | | 27 | | | | | D08052J | 7 | | 050-099 |
| 039 | 24 | | PK | 10-7 | 21-53-21 | D05744P | | 27 | | | | | D08052J | 7 | | 150-199, 275-299 |
| 040 | 24 | | PK | 11-0 | 21-53-21 | D05744P | | 17 | | | | | D08052J | 8 | | 050-099 |
| 040 | 24 | | PK | 10-7 | 21-53-21 | D05744P | | 17 | | | | | D08052J | 8 | | 150-199, 275-299 |
| 042 | 24 | | PK | 16-0 | 21-43-11 | D04296P | | 10 | | | | | D05062P | 7 | | 050-099 |
| 042 | 24 | | PK | 15-4 | 21-43-11 | D04296P | | 10 | | | | | D05062P | 7 | | 150-199, 275-299 |
| 043 | 24 | | PK | 16-0 | 21-43-11 | D04296P | | 11 | | | | | D05062P | 8 | | 050-099 |
| 043 | 24 | | PK | 15-4 | 21-43-11 | D04296P | | 11 | | | | | D05062P | 8 | | 150-199, 275-299 |
| 045 | 24 | | PK | 12-0 | 21-44-11 | D04296P | | 13 | | | | | D05744P | 11 | | 050-099 |
| 045 | 24 | | PK | 11-6 | 21-44-11 | D04296P | | 13 | | | | | D05744P | 11 | | 150-199, 275-299 |
| 046 | 22 | | PA | 16-0 | 21-44-11 | D04296P | | 14 | | | | | D05062P | 11 | | 050-099 |
| 046 | 22 | | PA | 15-4 | 21-44-11 | D04296P | | 14 | | | | | D05062P | 11 | | 150-199, 275-299 |
| 047 | 24 | | PK | 16-0 | 21-44-11 | D04296P | | 20 | | | | | D05062P | 12 | | 050-099 |
| 047 | 24 | | PK | 15-4 | 21-44-11 | D04296P | | 20 | | | | | D05062P | 12 | | 150-199, 275-299 |
| 048 | 24 | | PK | 16-0 | 21-44-11 | D04296P | | 28 | | | | | D05062P | 13 | | 050-099 |
| 048 | 24 | | PK | 15-4 | 21-44-11 | D04296P | | 28 | | | | | D05062P | 13 | | 150-199, 275-299 |
| 055 | 18 | | PA | 8-0 | 25-29-11 | D00006 | | = YEL | D | | | | D05744P | 23 | | 050-099 |
| 055 | 18 | | PA | 7-1 | 25-29-11 | D00006 | | = YEL | D | | | | D05744P | 23 | | 150-199, 275-299 |
| 056 | 18 | | PA | 4-0 | 25-29-11 | D00006 | | = WHT | | | | | G~ | A.. | E | 050-099 |
| | | | | | | | | D | | | | | D~ | | | |
| | | | | | | | | | | | | | 0~ | | | |
| | | | | | | | | | | | | | 1~ | | | |
| | | | | | | | | | | | | | 3~ | | | |
| | | | | | | | | | | | | | 14 | | | |
| 056 | 18 | | PA | 2-7 | 25-29-11 | D00006 | | = WHT | | | | | G~ | A.. | E | 150-199, |
| | | | | | | | | D | | | | | D~ | | | 275-299 |
| | | | | | | | | | | | | | 0~ | | | |
| | | | | | | | | | | | | | 1~ | | | |
| | | | | | | | | | | | | | 3~ | | | |
| | | | | | | | | | | | | | 14 | | | |
| 057 | 18 | | PA | 4-0 | 25-29-11 | D00006 | | = GRN | D | | | | GD01316 | S.. | E | 050-099 |
| 057 | 18 | | PA | 2-7 | 25-29-11 | D00006 | | = GRN | D | | | | GD01316 | S.. | E | 150-199, 275-299 |
| 059 | 20 | | PA | 16-0 | 21-31-21 | D05356P | | 14 | | | | | D04296P | 27 | | 050-099 |
| 059 | 20 | | PA | 15-2 | 21-31-21 | D05356P | | 14 | | | | | D04296P | 27 | | 150-199, 275-299 |
| 060 | 20 | | PA | 16-0 | 36-11-41 | D05356P | | 15 | | | | | D04296P | 15 | | 050-099 |
| 060 | 20 | | PA | 15-2 | 36-11-41 | D05356P | | 15 | | | | | D04296P | 15 | | 150-199, 275-299 |
| 061 | 22 | | PA | 24-0 | 28-42-11 | D05356P | | 16 | | | | | D05744P | 1 | | 050-099 |
| 061 | 22 | | PA | 23-8 | 28-42-11 | D05356P | | 16 | | | | | D05744P | 1 | | 150-199, 275-299 |
| 062 | 22 | | PA | 24-0 | 28-42-12 | D05356P | | 17 | | | | | D05744P | 2 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0620
Page 7
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0624 | 286T0624 | | | WSHLD HTR, (continued) | | | | | | | | | | | |
| 062 | 22 | | PA | | 23-8 | 28-42-12 | D05356P | | | | D05744P | | | | 150-199, 275-299 |
| 063 | 12 | | PA | | 8-0 | 30-41-12 | D04294J | | | | GD00512 | S.. | E | | 050-099 |
| 063 | 12 | | PA | | 6-10 | 30-41-12 | D04294J | | | | GD00512 | S.. | E | | 150-199, 275-299 |
| 064 | 12 | | PA | | 8-0 | 30-41-12 | D04294J | | | | GD00514 | A.. | E | | 050-099 |
| 064 | 12 | | PA | | 7-4 | 30-41-12 | D04294J | | | | GD00514 | A.. | E | | 150-199, 275-299 |
| 065 | 24 | | PK | | 24-0 | 28-42-31 | D05356P | | | | D05744P | | 3 | | 050-099 |
| 065 | 24 | | PK | | 23-8 | 28-42-31 | D05356P | | | | D05744P | | 3 | | 150-199, 275-299 |
| 066 | 20 | | PA | | 4-0 | 30-41-12 | D04294J | | | | GD00508 | D.. | E | | 050-099 |
| 066 | 20 | | PA | | 3-3 | 30-41-12 | D04294J | | | | GD00508 | D.. | E | | 150-199, 275-299 |
| 067 | 20 | | PA | | 4-0 | 30-41-12 | D04294J | | | | GD00508 | D.. | E | | 050-099 |
| 067 | 20 | | PA | | 3-3 | 30-41-12 | D04294J | | | | GD00508 | D.. | E | | 150-199, 275-299 |
| 068 | 20 | | PA | | 4-0 | 30-41-12 | D04294J | | | | GD00506 | A.. | E | | 050-099 |
| 068 | 20 | | PA | | 2-7 | 30-41-12 | D04294J | | | | GD00506 | A.. | E | | 150-199, 275-299 |
| 069 | 22 | | PA | | 24-0 | 21-44-21 | D05356P | | | | D05744P | | 14 | | 050-099 |
| 069 | 22 | | PA | | 23-8 | 21-44-21 | D05356P | | | | D05744P | | 14 | | 150-199, 275-299 |
| 070 | 24 | | PK | | 24-0 | SPARE | D05356P | | | | D05744P | | CAP | Y | ALL |
| 071 | 24 | | PK | | 24-0 | 21-44-21 | D05356P | | | | D05744P | | 12 | | 050-099 |
| 071 | 24 | | PK | | 23-8 | 21-44-21 | D05356P | | | | D05744P | | 12 | | 150-199, 275-299 |
| 072 | 22 | | PA | | 12-0 | 21-44-21 | D04296P | | | | D05744P | | 32 | | 050-099 |
| 072 | 22 | | PA | | 11-6 | 21-44-21 | D04296P | | | | D05744P | | 32 | | 150-199, 275-299 |
| 073 | 20 | | PA | | 17-0 | 30-41-12 | D04296P | | | | D04294J | | 16 | | 050-099 |
| 073 | 20 | | PA | | 16-2 | 30-41-12 | D04296P | | | | D04294J | | 16 | | 150-199, 275-299 |
| 074 | 20 | | PA | | 17-0 | 30-41-12 | D04296P | | | | D04294J | | 18 | | 050-099 |
| 074 | 20 | | PA | | 16-2 | 30-41-12 | D04296P | | | | D04294J | | 18 | | 150-199, 275-299 |
| 075 | 24 | | PK | | 11-0 | 21-51-21 | D05744P | | | | D08052J | | 15 | | 050-099 |
| 075 | 24 | | PK | | 10-7 | 21-51-21 | D05744P | | | | D08052J | | 15 | | 150-199, 275-299 |
| 076 | 22 | | PA | | 11-0 | 21-51-21 | D05744P | | | | D08052J | | 16 | | 050-099 |
| 076 | 22 | | PA | | 10-7 | 21-51-21 | D05744P | | | | D08052J | | 16 | | 150-199, 275-299 |
| 077 | 24 | | PK | | 24-0 | 21-53-21 | D05744P | | | | D05356P | | 10 | | 050-099 |
| 077 | 24 | | PK | | 23-8 | 21-53-21 | D05744P | | | | D05356P | | 10 | | 150-199, 275-299 |
| 078 | 24 | | PK | | 12-0 | 21-44-11 | D05744P | | | | D04296P | | 16 | | 050-099 |
| 078 | 24 | | PK | | 11-6 | 21-44-11 | D05744P | | | | D04296P | | 16 | | 150-199, 275-299 |
| 080 | 20 | | PA | | 16-0 | SPARE | D05062P | | | | D04296P | | 29 | | 050-099 |
| 080 | 18 | | PA | | 28-4 | 32-71-11 | D05062P | | DL | | D05192P | | 4 | DK | 150-199, 275-299 |
| 081 | 22 | | PA | | 29-0 | SPARE | D05356P | | | | D05192P | | 5 | | 050-099 |
| 081 | 22 | | PA | | 28-2 | SPARE | D05356P | | | | D05192P | | 5 | | 150-199, 275-299 |
| 082 | 24 | | PK | | 24-0 | 21-44-11 | D05062P | | | | D05744P | | 8 | | 050-099 |
| 082 | 24 | | PK | | 23-10 | 21-44-11 | D05062P | | | | D05744P | | 8 | | 150-199, 275-299 |
| 083 | 24 | | PK | | 24-0 | 21-44-11 | D05062P | | | | D05744P | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0620

Page 8

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0624 | 286T0624 | | | WSHLD HTR, (continued) | | | | | | | | | | | | |
| 083 | 24 | | PK | | 23-10 | 21-44-11 | D05062P | | 16 | | | | D05744P | 9 | | 150-199, 275-299 |
| 084 | 22 | | PA | | 12-0 | 21-44-21 | D04296P | | 42 | | | | D05744P | 33 | | 050-099 |
| 084 | 22 | | PA | | 11-6 | 21-44-21 | D04296P | | 42 | | | | D05744P | 33 | | 150-199, 275-299 |
| 100K | 20 | 8U | 1A | | 5-0 | 30-41-12 | SM00001 | | | 9 | | | D05872P | 1 | | 050-099 |
| 100K | 20 | 8U | 1A | | 3-4 | 30-41-12 | SM00001 | | | 9 | | | D05872P | 1 | | 150-199, 275-299 |
| 101O | 20 | 8U | 1A | | 0-0 | 30-41-12 | SM00002 | | | 9 | | | D05872P | 2 | | ALL |
| 102Y | 22 | 8U | 1B | | 0-0 | 30-41-12 | SM00003 | | | 9 | | | D05872P | 3 | | ALL |
| 103G | 22 | 8U | 1B | | 0-0 | 30-41-12 | SM00004 | | | 9 | | | D05872P | 4 | | ALL |
| 104R | 22 | 8U | 1C | | 0-0 | 30-41-12 | SM00005 | | | 9 | | | D05872P | 5 | | ALL |
| 105N | 22 | 8U | 1C | | 0-0 | 30-41-12 | SM00006 | | | 9 | | | D05872P | 6 | | ALL |
| 106 | 20 | PQ | Q | | 24-0 | 28-22-31 | D05356P | | 8 | | | | D05744P | 36 | | ALL |
| 106Z | | | Q | | 0-0 | 28-22-31 | D05356P | | | DED | | | D05744P | DED | | ALL |
| 107 | 20 | PQ | R | | 24-0 | 28-22-31 | D05356P | | 11 | | | | D05744P | 37 | | ALL |
| 107Z | | | R | | 0-0 | 28-22-31 | D05356P | | | DED | | | D05744P | DED | | ALL |
| 108 | 22 | PQ | S | | 24-0 | 28-22-31 | D05356P | | 1 | | | | D05744P | 15 | | ALL |
| 108Z | | | S | | 0-0 | 28-22-31 | D05356P | | | DED | | | D05744P | DED | | ALL |
| 109 | 22 | PQ | T | | 24-0 | 28-22-31 | D05356P | | 12 | | | | D05744P | 38 | | ALL |
| 109Z | | | T | | 0-0 | 28-22-31 | D05356P | | | DED | | | D05744P | DED | | ALL |
| 110 | 22 | PQ | U | | 24-0 | 28-22-31 | D05356P | | 13 | | | | D05744P | 39 | | ALL |
| 110Z | | | U | | 0-0 | 28-22-31 | D05356P | | | DED | | | D05744P | DED | | ALL |
| 201B | 12 | PB | A | | 30-0 | 30-41-12 | D04294J | | 4 | | | | SM00013 | 9 | | 050-099 |
| 201B | 12 | PB | A | | 28-5 | 30-41-12 | D04294J | | 4 | | | | SM00013 | 9 | | 150-199, 275-299 |
| 201R | 12 | PB | A | | 0-0 | 30-41-12 | D04294J | | 6 | | | | SM00014 | 9 | | ALL |
| 202B | 24 | PW | B | | 27-0 | 30-41-12 | TB0324F | A001 | 2 | | | | SM00015 | 9 | | 050-099 |
| 202B | 24 | PW | B | | 25-9 | 30-41-12 | TB0324F | A001 | 2 | | | | SM00015 | 9 | | 150-199, 275-299 |
| 202R | 24 | PW | B | | 0-0 | 30-41-12 | TB0324F | C001 | 2 | | | | SM00016 | 9 | | ALL |
| 202Z | | | B | | 0-0 | 30-41-12 | TB0324F | | | | FA | | SM00015 | DED | | ALL |
| 203B | 24 | PW | C | | 27-0 | 30-41-12 | TB0324F | A002 | 2 | | | | SM00017 | 9 | | 050-099 |
| 203B | 24 | PW | C | | 25-9 | 30-41-12 | TB0324F | A002 | 2 | | | | SM00017 | 9 | | 150-199, 275-299 |
| 203R | 24 | PW | C | | 0-0 | 30-41-12 | TB0324F | C002 | 2 | | | | SM00018 | 9 | | ALL |
| 203Z | | | C | | 0-0 | 30-41-12 | TB0324F | | | | FA | | SM00017 | DED | | ALL |
| 204B | 24 | PW | D | | 31-0 | 30-41-12 | TB0324F | A003 | 2 | | | | SM00003 | 9 | | 050-099 |
| 204B | 24 | PW | D | | 30-6 | 30-41-12 | TB0324F | A003 | 2 | | | | SM00003 | 9 | | 150-199, 275-299 |
| 204R | 24 | PW | D | | 0-0 | 30-41-12 | TB0324F | C003 | 2 | | | | SM00004 | 9 | | ALL |
| 204Z | | | D | | 0-0 | 30-41-12 | TB0324F | | | | FC | | SM00003 | DED | | ALL |
| 205B | 24 | PW | E | | 31-0 | 30-41-12 | TB0324F | A004 | 2 | | | | SM00005 | 9 | | 050-099 |
| 205B | 24 | PW | E | | 30-6 | 30-41-12 | TB0324F | A004 | 2 | | | | SM00005 | 9 | | 150-199, 275-299 |
| 205R | 24 | PW | E | | 0-0 | 30-41-12 | TB0324F | C004 | 2 | | | | SM00006 | 9 | | ALL |
| 205Z | | | E | | 0-0 | 30-41-12 | TB0324F | | | | FC | | SM00005 | DED | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0620

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|--------------|-----------------|----|-------|-------------------------------|------|----------|---------|-------|------|------|-------------|--------|-------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W0624 | 286T0624 | | | WSHLD HTR, (continued) | | | | | | | | | | | |
| 206B | 24 | PW | F | | 44-0 | 30-41-12 | TB0324F | A005 | 2 | | | | | 9 | ALL |
| 206R | 24 | PW | F | | 0-0 | 30-41-12 | TB0324F | C005 | 2 | | | | | 9 | ALL |
| 206Z | | | F | | 0-0 | 30-41-12 | TB0324F | | | | FE | | DED | | ALL |
| 207B | 24 | PW | G | | 19-0 | 21-31-21 | D04768J | | 13 | | | | 24 | | 050-099 |
| 207B | 24 | PW | G | | 18-1 | 21-31-21 | D04768J | | 13 | | | | 24 | | 150-199, 275-299 |
| 207R | 24 | PW | G | | 0-0 | 21-31-21 | D04768J | | 14 | | | | 25 | | ALL |
| 207Z | | | G | | 0-0 | 21-31-21 | D04768J | | 15 | | | | 26 | | ALL |
| 209B | 24 | PW | X | | 44-0 | 30-41-12 | TB0324F | A006 | 2 | | | | | 9 | ALL |
| 209R | 24 | PW | X | | 0-0 | 30-41-12 | TB0324F | C006 | 2 | | | | | 9 | ALL |
| 209Z | | | X | | 0-0 | 30-41-12 | TB0324F | | | | FE | | DED | | ALL |
| 210B | 12 | PB | J | | 17-0 | 30-41-12 | D04296P | | 56 | | | | 2 | | 050-099 |
| 210B | 12 | PB | J | | 16-2 | 30-41-12 | D04296P | | 56 | | | | 2 | | 150-199, 275-299 |
| 210R | 12 | PB | J | | 0-0 | 30-41-12 | D04296P | | 40 | | | | 1 | | ALL |
| 211B | 20 | PB | L | | 19-0 | 21-31-21 | D04768J | | 10 | | | | 21 | | 050-099 |
| 211B | 20 | PB | L | | 18-1 | 21-31-21 | D04768J | | 10 | | | | 21 | | 150-199, 275-299 |
| 211R | 20 | PB | L | | 0-0 | 21-31-21 | D04768J | | 11 | | | | 22 | | ALL |
| 212B | 22 | PB | M | | 11-0 | 21-51-22 | D05744P | | 5 | | | | 10 | | 050-099 |
| 212B | 22 | PB | M | | 10-7 | 21-51-22 | D05744P | | 5 | | | | 10 | | 150-199, 275-299 |
| 212R | 22 | PB | M | | 0-0 | 21-51-22 | D05744P | | 4 | | | | 9 | | ALL |
| 213B | 22 | PB | N | | 11-0 | 21-51-22 | D05744P | | 6 | | | | 11 | | 050-099 |
| 213B | 22 | PB | N | | 10-7 | 21-51-22 | D05744P | | 6 | | | | 11 | | 150-199, 275-299 |
| 213R | 22 | PB | N | | 0-0 | 21-51-22 | D05744P | | 7 | | | | 12 | | ALL |
| 214B | 24 | PL | P | | 11-0 | 21-51-21 | D05744P | | 22 | | | | 14 | | 050-099 |
| 214B | 24 | PL | P | | 10-7 | 21-51-21 | D05744P | | 22 | | | | 14 | | 150-199, 275-299 |
| 214R | 24 | PL | P | | 0-0 | 21-51-21 | D05744P | | 21 | | | | 13 | | ALL |
| 215B | 24 | PW | H | | 12-0 | 30-41-12 | TB0324F | A002 | 2 | | | | 15 | | 050-099 |
| 215B | 24 | PW | H | | 10-9 | 30-41-12 | TB0324F | A002 | 2 | | | | 15 | | 150-199, 275-299 |
| 215R | 24 | PW | H | | 0-0 | 30-41-12 | TB0324F | C002 | 2 | | | | 29 | | ALL |
| 215Z | | | H | | 0-0 | 30-41-12 | TB0324F | | | | FA | | 3 | | ALL |
| 216B | 24 | PW | I | | 12-0 | 30-41-12 | TB0324F | A004 | 2 | | | | 28 | | 050-099 |
| 216B | 24 | PW | I | | 10-9 | 30-41-12 | TB0324F | A004 | 2 | | | | 28 | | 150-199, 275-299 |
| 216R | 24 | PW | I | | 0-0 | 30-41-12 | TB0324F | C004 | 2 | | | | 17 | | ALL |
| 216Z | | | I | | 0-0 | 30-41-12 | TB0324F | | | | FC | | 5 | | ALL |
| 217B | 24 | PW | K | | 12-0 | 30-41-12 | TB0324F | A006 | 2 | | | | 25 | | 050-099 |
| 217B | 24 | PW | K | | 10-9 | 30-41-12 | TB0324F | A006 | 2 | | | | 25 | | 150-199, 275-299 |
| 217R | 24 | PW | K | | 0-0 | 30-41-12 | TB0324F | C006 | 2 | | | | 26 | | ALL |
| 217Z | | | K | | 0-0 | 30-41-12 | TB0324F | | | | FE | | 7 | | ALL |
| 801 | 20 | PA | | | 25-0 | SPARE | D05356P | | 24 | | | | 16 | | 050-099 |
| 801 | 20 | PA | | | 24-8 | SPARE | D05356P | | 24 | | | | 16 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0620

Page 10

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|--------|--------|--|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0624 | 286T0624 | | | WSHLD HTR, (continued) | | | | | | | | | | | | |
| A-A | | | | 0-0 | 30-41-12 | SM00013 | | | | 9 | | | D01666 | =1 | | ALL |
| A-B | | | | 0-0 | 30-41-12 | SM00013 | | | | 9 | | | D01668 | =1 | | ALL |
| A-C | | | | 0-0 | 30-41-12 | SM00014 | | | | 9 | | | D01670 | =1 | | ALL |
| A-D | | | | 0-0 | 30-41-12 | SM00017 | | | | 9 | | | D01912 | A | | ALL |
| A-E | | | | 0-0 | 30-41-12 | SM00018 | | | | 9 | | | D01912 | B | | ALL |
| A-F | | | | 0-0 | 30-41-12 | SM00015 | | | | 9 | | | D01914 | A | | ALL |
| A-G | | | | 0-0 | 30-41-12 | SM00016 | | | | 9 | | | D01914 | B | | ALL |
| A-H | | | | 0-0 | 30-41-12 | SM00007 | | | | 9 | | | D01672 | =1 | | ALL |
| A-I | | | | 0-0 | 30-41-12 | SM00008 | | | | 9 | | | D00872 | =1 | | ALL |
| A-J | | | | 0-0 | 30-41-12 | SM00009 | | | | 9 | | | D01924 | A | | ALL |
| A-K | | | | 0-0 | 30-41-12 | SM00010 | | | | 9 | | | D01924 | B | | ALL |
| A-L | | | | 0-0 | 30-41-12 | SM00011 | | | | 9 | | | D01922 | A | | ALL |
| A-M | | | | 0-0 | 30-41-12 | SM00012 | | | | 9 | | | D01922 | B | | ALL |
| W0626 | 286T0626 | | | L WW FIRE DET & BODY DUCT LEAK DET | | | | | | | | | | | | |
| 001R | 18 | | XG | 3-4 | 26-17-11 | D05044P | | | | 1 | | | D00942 | =1 | | ALL |
| 002R | 18 | | XG | 3-4 | 26-17-11 | D05044P | | | | 2 | | | D00944 | =1 | | ALL |
| 003R | 18 | | XG | 11-10 | 26-18-31 | D05044P | | | | 3 | | | D01506 | =1 | | ALL |
| W0627 | 286T0627 | | | VOICE RDR, SHELF TO CONTROL PANEL | | | | | | | | | | | | |
| 001 | 24 | | PK | 0-6 | 23-71-11 | SM00001 | | | | | W | | D00731 | R- | | ALL |
| 002 | 24 | | PK | 0-6 | 23-71-11 | SM00001 | | | | | W | | D00731 | Q- | | ALL |
| 003 | 24 | | PK | 0-6 | 23-71-11 | SM00001 | | | | | W | | D00731 | P- | | ALL |
| 004 | 20 | | PA | 35-0 | 23-71-11 | D04599J | | | | 4 | | | D00731 | F | | ALL |
| 006 | 24 | | PV | 35-0 | 23-71-11 | D04599J | | | | 6 | | | D00731 | W | | ALL |
| 006Z | | | AF | 0-0 | 23-71-11 | D04599J | | | | 5 | | | D00731 | V | | ALL |
| 008 | 24 | | PK | 35-0 | 23-71-11 | D04599J | | | | 8 | | | D00731 | H | | ALL |
| 009 | 24 | | PK | 35-0 | 23-71-11 | D04599J | | | | 9 | | | D00731 | G | | ALL |
| 010 | 24 | | PV | 35-0 | 23-71-11 | D04599J | | | | 10 | | | D00731 | L | | ALL |
| 010Z | | | AJ | 0-0 | 23-71-11 | D04599J | | | | 11 | | | D00731 | K | | ALL |
| 011 | 20 | | PA | 8-0 | 33-13-16 | TB0064G | | | | 1 | 2 | | D00731 | Y | | ALL |
| 012 | 24 | | PK | 35-0 | 23-71-11 | D04599J | | | | 12 | | | D00731 | A | | ALL |
| 013 | 24 | | PK | 35-0 | 23-71-11 | D04599J | | | | 13 | | | D00731 | B | | ALL |
| 014 | 22 | | PA | 35-0 | 23-71-11 | D04599J | | | | 14 | | | D00731 | C | | ALL |
| 015 | 24 | | PK | 35-0 | 23-71-11 | D04599J | | | | 15 | | | D00731 | D | | ALL |
| 016 | 24 | | PK | 35-0 | 23-71-11 | D04599J | | | | 16 | | | D00731 | E | | ALL |
| 017 | 20 | | PA | 7-0 | 33-13-16 | GD00267 | | | | A.. | 2 | | D00731 | Z | | ALL |
| 022 | 24 | | PK | 35-0 | 23-71-11 | D04599J | | | | 22 | | | D00731 | J- | | ALL |
| 023 | 24 | | PK | 35-0 | 23-71-11 | D04599J | | | | 23 | | | D00731 | H- | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0620

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0627 | 286T0627 | | | VOICE RDR, SHELF TO CONTROL PANEL (continued) | | | | | | | | | | | |
| 024 | 24 | | PK | | 35-0 | 23-71-11 | D04599J | 24 | | | D00731 | | I- | | ALL |
| 201B | 24 | | PW | IA | 1-6 | 23-71-11 | D00731 | | P | | D00731 | | G- | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 23-71-11 | D00731 | | N | | D00731 | | F- | | ALL |
| 201Z | | | | IA | 0-0 | 23-71-11 | D00731 | | M | | D00731 | | DED | | ALL |
| W0628 | 286T0628 | | | LANDING GEAR POSITION INDICATION-LEFT GEAR & ANTISKID | | | | | | | | | | | |
| 001 | 22 | | PA | | 79-1 | 30-11-11 | D05650P | 13 | | | SM00001 | | 9 | | 150-199, 275-299 |
| 002 | 22 | | PA | | 0-10 | SPARE | D04536J | 11 | | | SM00001 | | 9 | | 155-199, 275-278 |
| 002 | 22 | | PA | | 0-10 | 30-11-11 | D04536J | 11 | | | SM00001 | | 9 | | 280-299 |
| 003 | 22 | | PA | | 68-10 | 30-11-11 | D04536J | 7 | | | D05650P | 13 | | | 050-099 |
| 003 | 22 | | PA | | 0-10 | 30-11-11 | D04536J | 7 | | | SM00001 | | 9 | | 150-199, 275-299 |
| 004 | 22 | | PA | | 79-5 | SPARE | D04536J | 13 | | | D05650P | 5 | | | 155-157, 275-278 |
| 004 | 22 | | PA | | 79-5 | 30-11-11 | D04536J | 13 | | | D05650P | 5 | | | 280-299 |
| 006 | 24 | | PK | | 68-10 | 30-11-11 | D04536J | 12 | | | D05650P | 6 | | | 050-099 |
| 006 | 24 | | PK | | 79-5 | 30-11-11 | D04536J | 12 | | | D05650P | 6 | | | 150-199, 275-299 |
| 007 | 22 | | PA | | 68-10 | 30-11-11 | D04536J | 9 | | | D05650P | 7 | | | 050-099 |
| 007 | 22 | | PA | | 79-5 | 30-11-11 | D04536J | 9 | | | D05650P | 7 | | | 150-199, 275-299 |
| 008 | 22 | | PA | | 68-10 | 30-11-11 | D04536J | 10 | | | D05650P | 8 | | | 050-099 |
| 008 | 22 | | PA | | 79-5 | 30-11-11 | D04536J | 10 | | | D05650P | 8 | | | 150-199, 275-299 |
| 010 | 20 | | PA | | 57-0 | 33-43-11 | D05566J | 9 | | | D04536J | 15 | | | 050-099 |
| 010 | 16 | | PA | | 67-11 | 33-43-11 | D05566J | 15 | FL | | D04536J | 15 | FM | | 150-199, 275-299 |
| 011 | 22 | | PA | | 87-10 | 32-42-12 | D05350J | 11 | | | D05586J | 1 | | | 050-099 |
| 011 | 22 | | PA | | 97-6 | 32-42-12 | D05350J | 11 | | | D05586J | 1 | | | 150-199, 275-299 |
| 012 | 24 | | PK | | 57-6 | SPARE | D04962P | 5 | | | D08046J | 17 | | | 050-099 |
| 012 | 24 | | PK | | 67-6 | SPARE | D04962P | 5 | | | D08046J | 17 | | | 150-199, 275-299 |
| 013 | 22 | | PA | | 87-10 | 32-42-12 | D05350J | 13 | | | D05586J | 3 | | | 050-099 |
| 013 | 22 | | PA | | 97-6 | 32-42-12 | D05350J | 13 | | | D05586J | 3 | | | 150-199, 275-299 |
| 014 | 20 | | PA | | 96-10 | 33-31-11 | D05650P | 2 | | | D04654J | 10 | | | 050-099 |
| 014 | 20 | | PA | | 107-3 | 33-31-11 | D05650P | 2 | | | D04654J | 10 | | | 150-199, 275-299 |
| 019 | 22 | | PA | | 57-3 | SPARE | D04962P | 41 | | | D04536J | 31 | | | 050-099 |
| 019 | 22 | | PA | | 67-1 | SPARE | D04962P | 41 | | | D04536J | 31 | | | 150-199, 275-299 |
| 020 | 20 | | PA | | 84-8 | SPARE | D05350J | 23 | | | D04318J | 19 | | | 050-099 |
| 020 | 20 | | PA | | 94-8 | SPARE | D05350J | 23 | | | D04318J | 19 | | | 150-199, 275-299 |
| 021 | 22 | | PA | | 67-0 | SPARE | D05566J | 27 | | | D05190J | | CAP | Y | 050-099 |
| 021 | 22 | | PA | | 77-0 | SPARE | D05566J | 27 | | | D05190J | | CAP | Y | 150-199, 275-299 |
| 022 | 16 | | PA | | 3-9 | 33-31-11 | GD00852 | A.. | 2 | | D05608J | 6 | | | 050-099 |
| 022 | 16 | | PA | | 3-10 | 33-31-11 | GD00852 | A.. | 2 | | D05608J | 6 | | | 150-199, 275-299 |
| 023 | 20 | | PA | | 7-7 | 33-31-11 | D05608J | 5 | | | T00141 | | HV2 | E | 050-099 |
| 023 | 20 | | PA | | 7-2 | 33-31-11 | D05608J | 5 | | | T00141 | | HV2 | E | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0620
Page 12
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0628 | 286T0628 | | | LANDING GEAR POSITION INDICATION-LEFT GEAR & ANTISKID (continued) | | | | | | | | | | | | |
| 024 | 16 | | PA | 6-0 | 33-31-11 | GD00852 | A.. | 2 | | T00141 | GND | E | | 050-099 | | |
| 024 | 16 | | PA | 5-1 | 33-31-11 | GD00852 | A.. | 2 | | T00141 | GND | E | | 150-199, 275-299 | | |
| 025 | 16 | | PA | 7-7 | 33-31-11 | T00141 | LV | E | * | D05608J | 7 | | | 050-099 | | |
| 025 | 16 | | PA | 7-2 | 33-31-11 | T00141 | LV | E | * | D05608J | 7 | | | 150-199, 275-299 | | |
| 026 | 16 | | PA | 68-0 | 33-31-11 | T00141 | LV | E | * | D04654J | 5 | | | 050-099 | | |
| 026 | 16 | | PA | 67-5 | 33-31-11 | T00141 | LV | E | * | D04654J | 5 | | | 150-199, 275-299 | | |
| 027 | 16 | | PA | 4-4 | 33-31-11 | GD00668 | A.. | 2 | | D04654J | 6 | | | 050-099 | | |
| 027 | 16 | | PA | 4-5 | 33-31-11 | GD00668 | A.. | 2 | | D04654J | 6 | | | 150-199, 275-299 | | |
| 028 | 20 | | PA | 71-8 | 33-31-11 | D05608J | | 8 | | D04654J | 7 | | | 050-099 | | |
| 028 | 20 | | PA | 71-7 | 33-31-11 | D05608J | | 8 | | D04654J | 7 | | | 150-199, 275-299 | | |
| 029 | 20 | | PA | 71-8 | 33-31-11 | D05608J | | 9 | | D04654J | 8 | | | 050-099 | | |
| 029 | 20 | | PA | 71-7 | 33-31-11 | D05608J | | 9 | | D04654J | 8 | | | 150-199, 275-299 | | |
| 031 | 20 | | PA | 57-6 | 33-44-11 | D04962P | | 3 | | D08046J | 9 | | | 050-099 | | |
| 031 | 20 | | PA | 67-6 | 33-44-11 | D04962P | | 3 | | D08046J | 9 | | | 150-199, 275-299 | | |
| 033 | 22 | | PA | 57-3 | 29-11-12 | D04962P | | 16 | | D04536J | 2 | | | 050-099 | | |
| 033 | 22 | | PA | 67-1 | 29-11-12 | D04962P | | 16 | | D04536J | 2 | | | 150-199, 275-299 | | |
| 034 | 24 | | PK | 57-3 | 29-11-12 | D04962P | | 17 | | D04536J | 1 | | | 050-099 | | |
| 034 | 24 | | PK | 67-1 | 29-11-12 | D04962P | | 17 | | D04536J | 1 | | | 150-199, 275-299 | | |
| 035 | 22 | | PA | 57-3 | 29-11-12 | D04962P | | 18 | | D04536J | 4 | | | 050-099 | | |
| 035 | 22 | | PA | 67-1 | 29-11-12 | D04962P | | 18 | | D04536J | 4 | | | 150-199, 275-299 | | |
| 037 | 16 | | PA | 14-4 | 33-45-11 | D04962P | | 27 | | D05650P | 1 | FL | | 050-099 | | |
| 037 | 16 | | PA | 15-0 | 33-45-11 | D05650P | | 1 | FL | D04962P | 27 | | | 150-199, 275-299 | | |
| 038 | 16 | | PA | 14-4 | 33-45-11 | D04962P | | 28 | | D05650P | 4 | FL | | 050-099 | | |
| 038 | 16 | | PA | 15-0 | 33-45-11 | D05650P | | 4 | FL | D04962P | 28 | | | 150-199, 275-299 | | |
| 040 | 20 | | PA | 5-5 | 29-11-12 | GD00754 | D.. | 2 | | D04962P | 4 | | | 050-099 | | |
| 040 | 20 | | PA | 5-4 | 29-11-12 | GD00754 | D.. | 2 | | D04962P | 4 | | | 150-199, 275-299 | | |
| 041 | 24 | | PK | 57-6 | 21-53-12 | D04962P | | 11 | | D08046J | 1 | | | 050-099 | | |
| 041 | 24 | | PK | 67-6 | 21-53-12 | D04962P | | 11 | | D08046J | 1 | | | 150-199, 275-299 | | |
| 042 | 24 | | PK | 57-6 | 21-53-12 | D04962P | | 12 | | D08046J | 2 | | | 050-099 | | |
| 042 | 24 | | PK | 67-6 | 21-53-12 | D04962P | | 12 | | D08046J | 2 | | | 150-199, 275-299 | | |
| 043 | 24 | | PK | 57-6 | 21-53-12 | D04962P | | 13 | | D08046J | 3 | | | 050-099 | | |
| 043 | 24 | | PK | 67-6 | 21-53-12 | D04962P | | 13 | | D08046J | 3 | | | 150-199, 275-299 | | |
| 044 | 24 | | PK | 57-6 | 21-53-12 | D04962P | | 2 | | D08046J | 4 | | | 050-099 | | |
| 044 | 24 | | PK | 67-6 | 21-53-12 | D04962P | | 2 | | D08046J | 4 | | | 150-199, 275-299 | | |
| 045 | 24 | | PK | 57-6 | 21-53-12 | D04962P | | 20 | | D08046J | 5 | | | 050-099 | | |
| 045 | 24 | | PK | 67-6 | 21-53-12 | D04962P | | 20 | | D08046J | 5 | | | 150-199, 275-299 | | |
| 046 | 24 | | PK | 57-6 | 21-53-12 | D04962P | | 21 | | D08046J | 6 | | | 050-099 | | |
| 046 | 24 | | PK | 67-6 | 21-53-12 | D04962P | | 21 | | D08046J | 6 | | | 150-199, 275-299 | | |
| 048 | 22 | | PA | 24-0 | 78-36-21 | D04962P | | 7 | | D05566J | 14 | | | 050-099 | | |

WIRE LIST

D280T132

91-21-11

Section W0620

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0628 | 286T0628 | | | LANDING GEAR POSITION INDICATION-LEFT GEAR & ANTISKID (continued) | | | | | | | | | | | |
| 048 | 22 | | PA | | 21-5 | 78-36-21 | D04962P | | | | D05566J | | 14 | | 150-199, 275-299 |
| 049 | 24 | | PK | | 57-6 | 21-61-51 | D04962P | | | 24 | D08046J | | 7 | | 050-099 |
| 049 | 24 | | PK | | 67-6 | 21-61-51 | D04962P | | | 24 | D08046J | | 7 | | 150-199, 275-299 |
| 051 | 20 | | PA | | 57-3 | 27-81-21 | D04962P | | | 32 | D04536J | | 20 | | 050-099 |
| 051 | 20 | | PA | | 67-1 | 27-81-21 | D04962P | | | 32 | D04536J | | 20 | | 150-199, 275-299 |
| 052 | 18 | | PA | | 57-3 | 27-81-21 | D04962P | | | 33 | D04536J | | 21 | DK | 050-099 |
| 052 | 18 | | PA | | 67-1 | 27-81-21 | D04962P | | | 33 | D04536J | | 21 | DK | 150-199, 275-299 |
| 053 | 22 | | PA | | 42-6 | 27-81-21 | D04962P | | | 34 | SP01920 | | | 9 | 050-099 |
| 053 | 22 | | PA | | 54-4 | 27-81-21 | D04962P | | | 34 | SP01920 | | | 9 | 150-199, 275-299 |
| 054 | 18 | | PA | | 20-0 | 27-81-21 | SP01920 | | | | D04536J | | 22 | DK | 050-099 |
| 054 | 18 | | PA | | 21-4 | 27-81-21 | SP01920 | | | 9 | D04536J | | 22 | DK | 150-199, 275-299 |
| 059 | 18 | | PA | | 32-2 | 27-51-11 | SP01922 | | | 9 | D05418J | | 4 | | 050-099 |
| 059 | 18 | | PA | | 32-3 | 27-51-11 | SP01922 | | | 9 | D05418J | | 4 | | 150-199, 275-299 |
| 060 | 22 | | PA | | 54-8 | 27-51-11 | SP01922 | | | 9 | D05650P | | 10 | | 050-099 |
| 060 | 22 | | PA | | 66-7 | 27-51-11 | SP01922 | | | 9 | D05650P | | 10 | | 150-199, 275-299 |
| 061 | 18 | | PA | | 82-3 | 27-51-11 | D05418J | | | 3 | D05650P | | 11 | DL | 050-099 |
| 061 | 18 | | PA | | 92-11 | 27-51-11 | D05418J | | | 3 | D05650P | | 11 | DL | 150-199, 275-299 |
| 062 | 20 | | PA | | 82-3 | 27-51-11 | D05418J | | | 2 | D05650P | | 12 | | 050-099 |
| 062 | 20 | | PA | | 92-11 | 27-51-11 | D05418J | | | 2 | D05650P | | 12 | | 150-199, 275-299 |
| 063 | 20 | | PA | | 5-4 | 27-51-11 | D05418J | | | 1 | GD00794 | | D.. | 2 | 050-099 |
| 063 | 20 | | PA | | 5-5 | 27-51-11 | D05418J | | | 1 | GD00794 | | D.. | 2 | 150-199, 275-299 |
| 064 | 20 | | PA | | 5-4 | 27-51-11 | D05418J | | | 5 | GD00794 | | S.. | 2 | 050-099 |
| 064 | 20 | | PA | | 5-5 | 27-51-11 | D05418J | | | 5 | GD00794 | | S.. | 2 | 150-199, 275-299 |
| 067 | 24 | | PK | | 14-4 | 21-26-11 | D05650P | | | 9 | D04962P | | 15 | | 050-099 |
| 067 | 24 | | PK | | 15-0 | SPARE | D05650P | | | 9 | D04962P | | 15 | | 150-155, 162-165, 275-276 |
| 067 | 24 | | PK | | 15-0 | 21-26-11 | D05650P | | | 9 | D04962P | | 15 | | 156-157, 166-199, 277-299 |
| 090 | 18 | | PA | | 57-3 | 33-44-21 | D04962P | | | 22 | D04536J | | 16 | DK | 050-099 |
| 090 | 18 | | PA | | 67-1 | 33-44-21 | D04962P | | | 22 | D04536J | | 16 | DK | 150-199, 275-299 |
| 101 | 20 | | PA | | 57-6 | SPARE | D04962P | | | 40 | D08046J | | 8 | | 050-099 |
| 101 | 20 | | PA | | 67-6 | SPARE | D04962P | | | 40 | D08046J | | 8 | | 150-199, 275-299 |
| 103 | 22 | | PA | | 57-2 | SPARE | D05350J | | | 22 | D04536J | | 30 | | 050-099 |
| 104 | 22 | | PA | | 88-8 | SPARE | D05566J | | | 25 | D05586J | | 4 | | 050-099 |
| 104 | 22 | | PA | | 98-4 | SPARE | D05566J | | | 25 | D05586J | | 4 | | 150-199, 275-299 |
| 106 | 22 | | PA | | 57-3 | 29-11-12 | D04962P | | | 30 | D04536J | | 5 | | 050-099 |
| 106 | 22 | | PA | | 67-1 | 29-11-12 | D04962P | | | 30 | D04536J | | 5 | | 150-199, 275-299 |
| 107 | 20 | | PA | | 3-8 | 29-11-12 | GD03554 | | | D.. | 2 | | 6 | | 050-099 |
| 107 | 20 | | PA | | 3-3 | 29-11-12 | GD03554 | | | D.. | 2 | | 6 | | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0620
Page 14
Mar 14/2007



| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|-------------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0628 | 286T0628 | | | LANDING GEAR POSITION INDICATION-LEFT GEAR & ANTISKID (continued) | | | | | | | | | | | |
| 117 | 24 | | PK | | 23-0 | 32-61-14 | D04962P | | 23 | | | D05566J | 20 | | 050-099 |
| 117 | 24 | | PK | | 21-5 | 32-61-14 | D04962P | | 23 | | | D05566J | 20 | | 150-199, 275-299 |
| 201B | 22 | | PB | A | 67-0 | 32-61-12 | D05566J | | 3 | | | D05190J | 2 | | 050-099 |
| 201B | 22 | | PB | A | 77-0 | 32-61-12 | D05566J | | 3 | | | D05190J | 2 | | 150-199, 275-299 |
| 201R | 22 | | PB | A | 0-0 | 32-61-12 | D05566J | | 2 | | | D05190J | 1 | | ALL |
| 202B | 22 | | PB | B | 67-0 | 32-61-12 | D05566J | | 5 | | | D05190J | 4 | | 050-099 |
| 202B | 22 | | PB | B | 77-0 | 32-61-12 | D05566J | | 5 | | | D05190J | 4 | | 150-199, 275-299 |
| 202R | 22 | | PB | B | 0-0 | 32-61-12 | D05566J | | 4 | | | D05190J | 3 | | ALL |
| 203B | 22 | | PB | C | 67-0 | 32-61-12 | D05566J | | 7 | | | D05608J | 2 | | 050-099 |
| 203B | 22 | | PB | C | 77-0 | 32-61-12 | D05566J | | 7 | | | D05608J | 2 | | 150-199, 275-299 |
| 203R | 22 | | PB | C | 0-0 | 32-61-12 | D05566J | | 6 | | | D05608J | 1 | | ALL |
| 206B | 22 | | PB | F | 67-0 | 32-09-12 | D05566J | | 11 | | | D05190J | 11 | | 050-099 |
| 206B | 22 | | PB | F | 77-0 | 32-09-12 | D05566J | | 11 | | | D05190J | 11 | | 150-199, 275-299 |
| 206R | 22 | | PB | F | 0-0 | 32-09-12 | D05566J | | 10 | | | D05190J | 10 | | ALL |
| 207B | 22 | | PB | G | 85-9 | 32-09-12 | D05566J | | 13 | | | D04318J | 6 | | 050-099 |
| 207B | 22 | | PB | G | 95-6 | 32-09-12 | D05566J | | 13 | | | D04318J | 6 | | 150-199, 275-299 |
| 207R | 22 | | PB | G | 0-0 | 32-09-12 | D05566J | | 12 | | | D04318J | 5 | | ALL |
| 208B | 22 | | PB | H | 85-9 | 32-61-11 | D05566J | | 17 | | | D04318J | 2 | | 050-099 |
| 208B | 22 | | PB | H | 95-6 | 32-61-11 | D05566J | | 17 | | | D04318J | 2 | | 150-199, 275-299 |
| 208R | 22 | | PB | H | 0-0 | 32-61-11 | D05566J | | 16 | | | D04318J | 1 | | ALL |
| 209B | 22 | | PB | I | 85-9 | 32-61-11 | D05566J | | 19 | | | D04318J | 4 | | 050-099 |
| 209B | 22 | | PB | I | 95-6 | 32-61-11 | D05566J | | 19 | | | D04318J | 4 | | 150-199, 275-299 |
| 209R | 22 | | PB | I | 0-0 | 32-61-11 | D05566J | | 18 | | | D04318J | 3 | | ALL |
| 210B | 22 | | PB | J | 86-0 | 32-61-11 | D05566J | | 24 | | | D04654J | 2 | | 050-099 |
| 210B | 22 | | PB | J | 95-9 | 32-61-11 | D05566J | | 24 | | | D04654J | 2 | | 150-199, 275-299 |
| 210R | 22 | | PB | J | 0-0 | 32-61-11 | D05566J | | 23 | | | D04654J | 1 | | ALL |
| 213B | 20 | | PR | M | 84-8 | 32-42-11 | D05350J | | 8 | | | D04318J | 8 | | 050-099 |
| 213B | 20 | | PR | M | 94-8 | 32-42-11 | D05350J | | 8 | | | D04318J | 8 | | 150-199, 275-299 |
| 213R | 20 | | PR | M | 0-0 | 32-42-11 | D05350J | | 7 | | | D04318J | 7 | | ALL |
| 213Z | | | | M | 0-0 | 32-42-11 | D05350J | | 5 | | | D04318J | 15 | | ALL |
| 214B | 20 | | PR | N | 84-8 | 32-42-11 | D05350J | | 10 | | | D04318J | 10 | | 050-099 |
| 214B | 20 | | PR | N | 94-8 | 32-42-11 | D05350J | | 10 | | | D04318J | 10 | | 150-199, 275-299 |
| 214R | 20 | | PR | N | 0-0 | 32-42-11 | D05350J | | 9 | | | D04318J | 9 | | ALL |
| 214Z | | | | N | 0-0 | 32-42-11 | D05350J | | 6 | | | D04318J | 16 | | ALL |
| 215B | 20 | | PR | P | 66-1 | 32-42-11 | D05350J | | 17 | | | D05190J | 17 | | 050-099 |
| 215B | 20 | | PR | P | 76-2 | 32-42-11 | D05350J | | 17 | | | D05190J | 17 | | 150-199, 275-299 |
| 215R | 20 | | PR | P | 0-0 | 32-42-11 | D05350J | | 16 | | | D05190J | 16 | | ALL |
| 215Z | | | | P | 0-0 | 32-42-11 | D05350J | | 20 | | | D05190J | 14 | | ALL |
| 216B | 20 | | PR | R | 66-1 | 32-42-11 | D05350J | | 19 | | | D05190J | 19 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0620

Page 15

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0628 | 286T0628 | | | LANDING GEAR POSITION INDICATION-LEFT GEAR & ANTISKID (continued) | | | | | | | | | | | | |
| 216B | 20 | PR | R | 76-2 | 32-42-11 | D05350J | 19 | | | | D05190J | 19 | | | 150-199, 275-299 | |
| 216R | 20 | PR | R | 0-0 | 32-42-11 | D05350J | 18 | | | | D05190J | 18 | | | ALL | |
| 216Z | | | R | 0-0 | 32-42-11 | D05350J | 21 | | | | D05190J | 15 | | | ALL | |
| 217B | 24 | PL | W | 57-3 | 27-81-21 | D04962P | 36 | | | | D04536J | 24 | | | 050-099 | |
| 217B | 24 | PL | W | 67-1 | 27-81-21 | D04962P | 36 | | | | D04536J | 24 | | | 150-199, 275-299 | |
| 217R | 24 | PL | W | 0-0 | 27-81-21 | D04962P | 35 | | | | D04536J | 23 | | | ALL | |
| 218B | 22 | PB | D | 57-6 | 21-51-13 | D08046J | 13 | | | | D04962P | 10 | | | 050-099 | |
| 218B | 22 | PB | D | 67-6 | 21-51-13 | D08046J | 13 | | | | D04962P | 10 | | | 150-199, 275-299 | |
| 218R | 22 | PB | D | 0-0 | 21-51-13 | D08046J | 14 | | | | D04962P | 31 | | | ALL | |
| 219B | 22 | PB | E | 57-6 | 21-51-13 | D08046J | 15 | | | | D04962P | 26 | | | 050-099 | |
| 219B | 22 | PB | E | 67-6 | 21-51-13 | D08046J | 15 | | | | D04962P | 26 | | | 150-199, 275-299 | |
| 219R | 22 | PB | E | 0-0 | 21-51-13 | D08046J | 16 | | | | D04962P | 29 | | | ALL | |
| 222 | 20 | PA | | 90-0 | 31-31-22 | D05586J | 2 | | | | D05566J | 8 | | | 050-099 | |
| 222 | 20 | PA | | 98-4 | 31-31-22 | D05566J | 8 | | | | D05586J | 2 | | | 150-199, 275-299 | |
| 223B | 22 | PR | AE | 87-0 | 31-31-22 | D05586J | 6 | | | | D05566J | 29 | | | 050-099 | |
| 223B | 22 | PR | AE | 98-4 | 31-31-22 | D05566J | 29 | | | | D05586J | 6 | | | 150-199, 275-299 | |
| 223R | 22 | PR | AE | 0-0 | 31-31-22 | D05586J | 5 | | | | D05566J | 28 | | | 050-099 | |
| 223R | 22 | PR | AE | 0-0 | 31-31-22 | D05566J | 28 | | | | D05586J | 5 | | | 150-199, 275-299 | |
| 223Z | | | AE | 0-0 | 31-31-22 | D05586J | 7 | | | | D05566J | 30 | | | 050-099 | |
| 223Z | | | AE | 0-0 | 31-31-22 | D05566J | 30 | | | | D05586J | 7 | | | 150-199, 275-299 | |
| 241B | 20 | PR | JA | 79-0 | 32-45-14 | D05566J | 21 | | | | D08272J | 8 | | | 050-099 | |
| 241B | 20 | PR | JA | 77-3 | 32-45-14 | D05566J | 21 | | | | D08272J | 8 | | | 150-199 | |
| 241B | 20 | PR | JA | 81-6 | 32-45-14 | D06808J | 1 | | | | D08272J | 8 | | | 275-299 | |
| 241R | 20 | PR | JA | 0-0 | 32-45-14 | D05566J | 22 | | | | D08272J | 9 | | | 050-099, 150-199 | |
| 241R | 20 | PR | JA | 0-0 | 32-45-14 | D06808J | 2 | | | | D08272J | 9 | | | 275-299 | |
| 241Z | | | JA | 0-0 | 32-45-14 | D05566J | 1 | | | | D08272J | 10 | | | 050-099, 150-199 | |
| 241Z | | | JA | 0-0 | 32-45-14 | D06808J | 3 | | | | D08272J | 10 | | | 275-299 | |
| 242B | 20 | PR | JB | 79-0 | 32-45-14 | D05566J | 31 | | | | D08272J | 11 | | | 050-099 | |
| 242B | 20 | PR | JB | 77-3 | 32-45-14 | D05566J | 31 | | | | D08272J | 11 | | | 150-199 | |
| 242B | 20 | PR | JB | 81-6 | 32-45-14 | D06808J | 4 | | | | D08272J | 11 | | | 275-299 | |
| 242R | 20 | PR | JB | 0-0 | 32-45-14 | D05566J | 32 | | | | D08272J | 12 | | | 050-099, 150-199 | |
| 242R | 20 | PR | JB | 0-0 | 32-45-14 | D06808J | 5 | | | | D08272J | 12 | | | 275-299 | |
| 242Z | | | JB | 0-0 | 32-45-14 | D05566J | 26 | | | | D08272J | 13 | | | 050-099, 150-199 | |
| 242Z | | | JB | 0-0 | 32-45-14 | D06808J | 6 | | | | D08272J | 13 | | | 275-299 | |
| 243B | 20 | PR | JC | 79-0 | 32-45-14 | D05566J | 33 | | | | D06342J | 9 | | | 050-099 | |
| 243B | 20 | PR | JC | 77-3 | 32-45-14 | D05566J | 33 | | | | D06342J | 9 | | | 150-199 | |
| 243B | 20 | PR | JC | 81-6 | 32-45-14 | D06808J | 7 | | | | D06342J | 9 | | | 275-299 | |
| 243R | 20 | PR | JC | 0-0 | 32-45-14 | D05566J | 34 | | | | D06342J | 10 | | | 050-099, 150-199 | |
| 243R | 20 | PR | JC | 0-0 | 32-45-14 | D06808J | 8 | | | | D06342J | 10 | | | 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W0620
Page 16
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0628 | 286T0628 | | | LANDING GEAR POSITION INDICATION-LEFT GEAR & ANTISKID (continued) | | | | | | | | | | | | |
| 243Z | | | JC | 0-0 | 32-45-14 | D05566J | | 35 | | | | | D06342J | 11 | | 050-099, 150-199 |
| 243Z | | | JC | 0-0 | 32-45-14 | D06808J | | 9 | | | | | D06342J | 11 | | 275-299 |
| 244B | 20 | PR | JD | 79-0 | 32-45-14 | D05566J | | 36 | | | | | D06342J | 12 | | 050-099 |
| 244B | 20 | PR | JD | 77-3 | 32-45-14 | D05566J | | 36 | | | | | D06342J | 12 | | 150-199 |
| 244B | 20 | PR | JD | 81-6 | 32-45-14 | D06808J | | 10 | | | | | D06342J | 12 | | 275-299 |
| 244R | 20 | PR | JD | 0-0 | 32-45-14 | D05566J | | 37 | | | | | D06342J | 13 | | 050-099, 150-199 |
| 244R | 20 | PR | JD | 0-0 | 32-45-14 | D06808J | | 11 | | | | | D06342J | 13 | | 275-299 |
| 244Z | | | JD | 0-0 | 32-45-14 | D05566J | | 38 | | | | | D06342J | 14 | | 050-099, 150-199 |
| 244Z | | | JD | 0-0 | 32-45-14 | D06808J | | 12 | | | | | D06342J | 14 | | 275-299 |
| 301B | 24 | PM | X | 57-3 | 27-81-21 | D04962P | | 38 | | | | | D04536J | 26 | | 050-099 |
| 301B | 24 | PM | X | 67-1 | 27-81-21 | D04962P | | 38 | | | | | D04536J | 26 | | 150-199, 275-299 |
| 301R | 24 | PM | X | 0-0 | 27-81-21 | D04962P | | 37 | | | | | D04536J | 25 | | ALL |
| 301Y | 24 | PM | X | 0-0 | 27-81-21 | D04962P | | 39 | | | | | D04536J | 27 | | ALL |
| 306B | 20 | VH | MF | 93-4 | 27-62-11 | D05190J | | 12 | | | | | D05650P | 16 | | ALL |
| 306R | 20 | VH | MF | 0-0 | 27-62-11 | D05190J | | 13 | | | | | D05650P | 15 | | ALL |
| 306Y | 20 | VH | MF | 0-0 | 27-62-11 | D05190J | | 9 | | | | | D05650P | 23 | | ALL |
| 306Z | | | MF | 0-0 | 27-62-11 | D05190J | | | = CC | M | | | D05650P | 24 | | ALL |
| 451G | 22 | XU | S | 82-4 | 32-46-11 | D05292J | | 2 | | 4E | | | D04318J | 12 | 4H | 050-099 |
| 451G | 22 | XU | S | 92-1 | 32-46-11 | D05292J | | 2 | | 4E | | | D04318J | 12 | 4H | 150-199, 275-299 |
| 451W | 22 | XU | S | 0-0 | 32-46-11 | D05292J | | 1 | | 4I | | | D04318J | 11 | 4L | ALL |
| 452G | 22 | XU | T | 82-4 | 32-46-11 | D05292J | | 4 | | 4E | | | D04318J | 14 | 4H | 050-099 |
| 452G | 22 | XU | T | 92-1 | 32-46-11 | D05292J | | 4 | | 4E | | | D04318J | 14 | 4H | 150-199, 275-299 |
| 452W | 22 | XU | T | 0-0 | 32-46-11 | D05292J | | 3 | | 4I | | | D04318J | 13 | 4L | ALL |
| 453G | 22 | XU | U | 62-6 | 32-46-11 | D05292J | | 6 | | 4E | | | D05190J | 6 | 4H | 050-099 |
| 453G | 22 | XU | U | 73-7 | 32-46-11 | D05292J | | 6 | | 4E | | | D05190J | 6 | 4H | 150-199, 275-299 |
| 453W | 22 | XU | U | 0-0 | 32-46-11 | D05292J | | 5 | | 4I | | | D05190J | 5 | 4L | ALL |
| 454G | 22 | XU | V | 62-6 | 32-46-11 | D05292J | | 8 | | 4E | | | D05190J | 8 | 4H | 050-099 |
| 454G | 22 | XU | V | 73-7 | 32-46-11 | D05292J | | 8 | | 4E | | | D05190J | 8 | 4H | 150-199, 275-299 |
| 454W | 22 | XU | V | 0-0 | 32-46-11 | D05292J | | 7 | | 4I | | | D05190J | 7 | 4L | ALL |
| W0629 | 286T0629 | | | CAPT AUD SELECT PNL TO P15,CONTROL COLUMN,INTPH SPKR AND MIC | | | | | | | | | | | | |
| 001 | 22 | PA | | 17-0 | 23-51-11 | D00257 | | 3 | | | | | SP00131 | 9 | | ALL |
| 002 | 24 | PK | | 19-0 | 23-51-11 | D00257 | | 5 | | | | | TB0207F | A008 2 | | ALL |
| 003 | 24 | PK | | 19-0 | 23-51-11 | D00257 | | 6 | | | | | TB0207G | 11 2 | | ALL |
| 004 | 24 | PK | | 19-0 | 23-51-11 | D00257 | | 7 | | | | | TB0207F | C008 2 | | ALL |
| 005 | 20 | PA | | 9-0 | 23-51-11 | D00257 | | 4 | | | | | GD02464 | D.. 2 | | ALL |
| 007 | 24 | PV | AG | 18-0 | 23-51-11 | D00257 | | 18 | | | | | D00261 | 1 | | ALL |
| 007Z | | | AG | 0-0 | 23-51-11 | D00257 | | 17 | | | | | D00261 | 2 | | ALL |
| 008 | 24 | PK | | 18-0 | 23-51-11 | D00257 | | 19 | | | | | D00261 | 6 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0620

Page 17

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0629 | 286T0629 | | | CAPT AUD SELECT PNL TO P15,CONTROL COLUMN,INTPH SPKR AND MIC (continued) | | | | | | | | | | | |
| 009 | 24 | | PK | | 18-0 | 23-51-11 | D00257 | | 20 | | D00261 | | 4 | | ALL |
| 010 | 24 | | PK | | 18-0 | 23-51-11 | D00257 | | 21 | | D00261 | | 7 | | ALL |
| 011 | 24 | | PK | | 1-0 | 23-51-11 | D00257 | | 23 | | D00257 | | 24 | | ALL |
| 012 | 24 | | PV | AL | 18-0 | 23-51-11 | D00257 | | 16 | | D00861 | | 3 | \$D | ALL |
| 012Z | | | | AL | 0-0 | 23-51-11 | D00257 | | 15 | | D00861 | | 4 | \$D | ALL |
| 013 | 24 | | PV | AM | 19-0 | 23-51-11 | D00257 | | 9 | | D01373 | | A | | ALL |
| 013Z | | | | AM | 0-0 | 23-51-11 | D00257 | | 8 | | D01373 | | B | | ALL |
| 014 | 18 | | PA | | 9-0 | 33-13-18 | D00257 | | 1 | DK | SP02276 | | | | 050-099, 150-155, 162-165, 275-276 |
| 015 | 18 | | PA | | 1-8 | 33-13-18 | D00257 | | 2 | DK | GD04452 | A.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 023 | 20 | | PA | | 6-0 | 23-51-11 | D01353 | | 11 | | GD00027 | A.. | 2 | | ALL |
| 024 | 24 | | PK | | 17-0 | 23-51-11 | D00257 | | 29 | | SP00481 | | W | | 050-099, 153-199, 275-299 |
| 024 | 24 | | PK | | 17-0 | 23-51-11 | D00257 | | 29 | | SP00901 | | W | | 150 |
| 024 | 24 | | PV | AY | 17-0 | 23-51-11 | D01353 | | 10 | | SP00481 | | W | | 151-152 |
| 024Z | | | | AY | 0-0 | 23-51-11 | D01353 | REF | | IC | D00257 | REF | | FC | 151-152 |
| 025 | 24 | | PK | | 19-0 | 23-51-11 | D01373 | | E | | D00257 | | 31 | | ALL |
| 026 | 20 | | PA | | 5-0 | 23-51-11 | D01373 | | F | | GD00027 | D.. | 2 | | 050-099 |
| 026 | 20 | | PA | | 6-0 | 23-51-11 | D01373 | | F | | GD00027 | D.. | 2 | | 150-199, 275-299 |
| 027 | 18 | | PA | | 1-6 | 33-13-11 | D01353 | | 1 | DK | SP03774 | | W | | ALL |
| 028 | 18 | | PA | | 1-6 | 33-13-11 | D01353 | | 2 | DK | SP03776 | | W | | ALL |
| 030 | 24 | | PK | | 15-0 | 23-51-11 | D01353 | | 7 | | SP00481 | | W | | ALL |
| 201B | 24 | | PL | IA | 18-0 | 23-51-11 | D00257 | | 13 | | D00861 | | 2 | \$D | ALL |
| 201R | 24 | | PL | IA | 0-0 | 23-51-11 | D00257 | | 14 | | D00861 | | 1 | \$D | ALL |
| 203B | 24 | | PW | IC | 17-0 | 23-51-11 | D00257 | | 12 | | D01353 | | 3 | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 23-51-11 | D00257 | | 10 | | D01353 | | 4 | | ALL |
| 203Z | | | | IC | 0-0 | 23-51-11 | D00257 | | 11 | | D01353 | | 5 | | 050-099, 150 |
| 203Z | | | | IC | 0-0 | 23-51-11 | D00257 | REF | | FC | D01353 | REF | | IC | 151-199, 275-299 |
| 206B | 18 | | PB | IF | 0-0 | 33-13-18 | D00257 | | 2 | DK | SP05000 | | 9 | | 156-157, 166-199, 277-299 |
| 206R | 18 | | PB | IF | 9-0 | 33-13-18 | D00257 | | 1 | DK | SP02276 | | 9 | | 156-157, 166-199, 277-299 |
| FRA | | | | | 0-0 | 23-51-11 | D01353 | REF | | IC | D01353 | | 5 | | 151-199, 275-299 |
| FRB | | | | | 0-0 | 23-51-11 | D00257 | REF | | FC | D00257 | | 11 | | 151-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0620
Page 18 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|------|------|---------|-------------|-----|-----|---------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0631 | 286T0631 | | | F/O AUD SELECT PNL TO P16,CONTROL COLUMN,INTPH SPKR AND MIC | | | | | | | | | | | | | | | |
| 001 | 22 | | PA | | 32-0 | 23-51-21 | D00259 | | 3 | | | | | | SP00129 | | 9 | | ALL |
| 002 | 24 | | PK | | 27-0 | 23-51-21 | D00259 | | 5 | | | | | | TB0307F | A008 | 2 | | ALL |
| 003 | 24 | | PK | | 27-0 | 23-51-21 | D00259 | | 6 | | | | | | TB0307G | 11 | 2 | | ALL |
| 004 | 24 | | PK | | 27-0 | 23-51-21 | D00259 | | 7 | | | | | | TB0307F | C008 | 2 | | ALL |
| 005 | 20 | | PA | | 14-0 | 23-51-21 | D00259 | | 4 | | | | | | GD02466 | D.. | 2 | | ALL |
| 007 | 24 | | PV | AG | 22-0 | 23-51-21 | D00259 | | 18 | | | | | | D00263 | | 1 | | ALL |
| 007Z | | | | AG | 0-0 | 23-51-21 | D00259 | | 17 | | | | | | D00263 | | 2 | | ALL |
| 008 | 24 | | PK | | 22-0 | 23-51-21 | D00259 | | 19 | | | | | | D00263 | | 6 | | ALL |
| 009 | 24 | | PK | | 22-0 | 23-51-21 | D00259 | | 20 | | | | | | D00263 | | 4 | | ALL |
| 010 | 24 | | PK | | 22-0 | 23-51-21 | D00259 | | 21 | | | | | | D00263 | | 7 | | ALL |
| 011 | 24 | | PK | | 2-0 | 23-51-21 | D00259 | | 23 | | | | | | D00259 | | 24 | | ALL |
| 012 | 24 | | PV | AL | 23-0 | 23-51-21 | D00259 | | 16 | | | | | | D00863 | | 3 | \$D | ALL |
| 012Z | | | | AL | 0-0 | 23-51-21 | D00259 | | 15 | | | | | | D00863 | | 4 | \$D | ALL |
| 013 | 24 | | PV | AM | 39-0 | 23-51-21 | D00259 | | 26 | | | | | | D01359 | | 7 | | 050-099, 275-299 |
| 013 | 24 | | PV | AM | 39-0 | 23-51-21 | D01359 | | 7 | | | | | | D00259 | | 26 | | 150-199 |
| 013Z | | | | AM | 0-0 | 23-51-21 | D00259 | | 25 | | | | | | D01359 | | 6 | | 050-099, 275-299 |
| 013Z | | | | AM | 0-0 | 23-51-21 | D01359 | | 6 | | | | | | D00259 | | 25 | | 150-199 |
| 014 | 24 | | PV | AN | 22-6 | 23-51-21 | D00259 | | 9 | | | | | | D01375 | | A | | ALL |
| 014Z | | | | AN | 0-0 | 23-51-21 | D00259 | | 8 | | | | | | D01375 | | B | | ALL |
| 015 | 24 | | PV | AO | 11-0 | 23-51-41 | D01359 | | 4 | | | | | | SP00337 | | VL | | ALL |
| 015Z | | | | AO | 0-0 | 23-51-41 | D01359 | | 5 | | | | | | SP00337 | REF | | 37 | ALL |
| 016 | 18 | | PA | | 12-4 | 33-13-18 | D00259 | | 1 | DK | | | | | SP02286 | | 9 | | 050-099, 150-155, 162-165, 275-276 |
| 017 | 18 | | PA | | 2-0 | 33-13-18 | D00259 | | 2 | DK | | | | | GD04456 | | A.. | 2 | 050-099, 150-155, 162-165, 275-276 |
| 023 | 20 | | PA | | 9-0 | 23-51-21 | D01355 | | 11 | | | | | | GD00073 | | A.. | 2 | ALL |
| 024 | 24 | | PK | | 15-0 | 23-51-21 | D00259 | | 29 | | | | | | SP00507 | | W | | 050-099 |
| 024 | 24 | | PK | | 21-0 | 23-51-21 | D00259 | | 29 | | | | | | SP00903 | | W | | 150 |
| 024 | 24 | | PV | AX | 21-0 | 23-51-21 | D01355 | | 10 | | | | | | SP00507 | | W | | 151-152 |
| 024 | 24 | | PK | | 14-0 | 23-51-21 | D00259 | | 29 | | | | | | SP00507 | | W | | 153-199 |
| 024 | 24 | | PK | | 16-0 | 23-51-21 | D00259 | | 29 | | | | | | SP00507 | | W | | 275-299 |
| 024Z | | | | AX | 0-0 | 23-51-21 | D01355 | | REF | | IC | | | | D00259 | REF | | FC | 151-152 |
| 026 | 24 | | PK | | 26-0 | 23-51-21 | D01355 | | 7 | | | | | | SP00507 | | W | | 050-099, 153-199 |
| 026 | 24 | | PK | | 27-0 | 23-51-21 | D01355 | | 7 | | | | | | SP00903 | | W | | 150 |
| 026 | 24 | | PK | | 27-0 | 23-51-21 | D01355 | | 7 | | | | | | SP00481 | | W | | 151-152 |
| 026 | 24 | | PK | | 28-0 | 23-51-21 | D01355 | | 7 | | | | | | SP00507 | | W | | 275-299 |
| 027 | 18 | | PA | | 1-6 | 33-13-13 | D01355 | | 1 | DK | | | | | SP03778 | | W | | ALL |
| 028 | 18 | | PA | | 1-6 | 33-13-13 | D01355 | | 2 | DK | | | | | SP03780 | | W | | 050-099, 150-156, 162-166, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0630

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0631 | 286T0631 | | | F/O AUD SELECT PNL TO P16,CONTROL COLUMN,INTPH SPKR AND MIC (continued) | | | | | | | | | | | |
| 028 | 18 | | PA | | 7-1 | 33-13-13 | D01355 | 2 | DK | | GD04510 | A.. | 2 | | 157, 167-199, 277-299 |
| 029 | 20 | | PA | | 4-2 | 23-51-21 | D01375 | | F | | GD00073 | D.. | 2 | | ALL |
| 030 | 24 | | PK | | 22-6 | 23-51-21 | D01375 | | E | | D00259 | | 31 | | ALL |
| 201B | 24 | | PL | IA | 23-0 | 23-51-21 | D00259 | | 13 | | D00863 | | 2 | \$D | ALL |
| 201R | 24 | | PL | IA | 0-0 | 23-51-21 | D00259 | | 14 | | D00863 | | 1 | \$D | ALL |
| 203B | 24 | | PW | IC | 21-0 | 23-51-21 | D00259 | | 12 | | D01355 | | 3 | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 23-51-21 | D00259 | | 10 | | D01355 | | 4 | | ALL |
| 203Z | | | | IC | 0-0 | 23-51-21 | D00259 | | 11 | | D01355 | | 5 | | 050-099, 150 |
| 203Z | | | | IC | 0-0 | 23-51-21 | D00259 | REF | | FC | D01355 | REF | | IC | 151-199, 275-299 |
| 205B | 18 | | PB | IE | 0-0 | 33-13-18 | D00259 | 2 | DK | | SP05010 | | 9 | | 156-157, 166-199, 277-299 |
| 205R | 18 | | PB | IE | 12-4 | 33-13-18 | D00259 | 1 | DK | | SP02286 | | 9 | | 156-157, 166-199, 277-299 |
| 926 | 24 | | PK | | 10-0 | 23-51-11 | SP00481 | | | W | SP00901 | | | W | 150 |
| FRA | | | | | 0-0 | 23-51-21 | D01355 | | 5 | | D01355 | REF | | IC | 151-199, 275-299 |
| FRB | | | | | 0-0 | 23-51-21 | D00259 | REF | | FC | D00259 | | 11 | | 151-199 |
| FRB | | | | | 0-0 | 23-51-21 | D00259 | | 11 | | D00259 | REF | | FC | 275-299 |
| W0632 | 286T0632 | | | FWD FLDK INSTR PNL,UTIL LTS,WARN & CAUTION LTS | | | | | | | | | | | |
| 001 | 22 | | PA | | 17-11 | SPARE | D05282P | 25 | | | M00635 | CAP | Y | | 152, 154, 156, 162, 166-199 |
| 002 | 20 | | PA | | 9-5 | SPARE | GD00434 | | CAP | Y | M00635 | CAP | Y | | 152, 154, 156, 162, 166-199 |
| 005 | 22 | | PA | | 1-9 | 33-13-18 | D05282P | 17 | | | SM00001 | | 9 | | ALL |
| 006 | 22 | | PA | | 21-7 | 33-13-18 | D03734 | 12 | | | SM00001 | | 9 | | ALL |
| 007 | 16 | | PA | | 1-0 | 33-13-18 | D03734 | 11 | FM | | GD04370 | A.. | E | | ALL |
| 008 | 20 | | PA | | 6-9 | 33-13-18 | D03734 | 7 | | | GD00096 | S.. | 2 | | ALL |
| 009 | 18 | | PA | | 1-0 | 33-13-18 | D03734 | 2 | DK | | SP02288 | | 9 | | ALL |
| 010 | 22 | | PA | | 18-5 | 33-13-18 | D03736 | 12 | | | SM00001 | | 9 | | ALL |
| 011 | 16 | | PA | | 1-3 | 33-13-18 | D03736 | 11 | FM | | GD04456 | A.. | 2 | | ALL |
| 012 | 20 | | PA | | 1-10 | 33-13-18 | D03736 | 7 | | | GD04456 | S.. | 2 | | ALL |
| 013 | 18 | | PA | | 2-0 | 33-13-18 | D03736 | 2 | DK | | SP02270 | | 9 | | 050-099, 150-155, 162-165, 275-276 |
| 013 | 18 | | PA | | 0-9 | 33-13-18 | D03736 | 2 | DK | | SP02270 | | 9 | | 156-157, 166-199, 277-299 |
| 016 | 22 | | PA | | 21-5 | 33-13-18 | D03756 | 12 | | | SM00001 | | 9 | | ALL |
| 017 | 16 | | PA | | 1-0 | 33-13-18 | D03756 | 11 | FM | | GD04370 | A.. | E | | ALL |
| 018 | 20 | | PA | | 6-8 | 33-13-18 | D03756 | 7 | | | GD00096 | S.. | 2 | | ALL |
| 019 | 18 | | PA | | 1-0 | 33-13-18 | D03756 | 2 | DK | | SP02282 | | 9 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0630
Page 2
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|---|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0632 | 286T0632 | | | FWD FLDK INSTR PNL,UTIL LTS,WARN & CAUTION LTS (continued) | | | | | | | | | | | | | |
| 021 | 22 | | PA | 14-10 | 33-16-26 | D05282P | 21 | | | | | | L00755 | 1 | B | | ALL |
| 022 | 22 | | PA | 14-10 | 33-16-26 | D05282P | 22 | | | | | | L00755 | 3 | B | | ALL |
| 031 | 24 | | PK | 14-2 | 33-14-21 | D05395J | 11 | | | | | | D04990P | 11 | | | ALL |
| 036 | 24 | | PK | 1-7 | 33-14-31 | D04990P | 13 | | | | | | SM00004 | | S | | ALL |
| 037 | 24 | | PK | 15-9 | 33-14-31 | TB5100 | =P | E | | | | | SM00004 | | S | | ALL |
| 038 | 20 | | PA | 12-0 | 33-14-31 | TB5100 | =G | E | | | | | GD00434 | A.. | 2 | | ALL |
| 039 | 24 | | PK | 25-0 | 33-14-31 | TB5102 | =P | E | | | | | SM00004 | | S | | ALL |
| 040 | 20 | | PA | 2-10 | 33-14-31 | TB5102 | =G | E | | | | | GD00027 | A.. | 2 | | ALL |
| 041 | 24 | | PK | 12-10 | 33-14-31 | TB5104 | =P | E | | | | | D04990P | 14 | | | ALL |
| 042 | 20 | | PA | 3-3 | 33-14-31 | TB5104 | =G | E | | | | | GD04510 | A.. | 2 | | ALL |
| 045 | 24 | | PK | 14-2 | 33-13-11 | D04990P | 12 | | | | | | D05395J | 12 | | | ALL |
| 046 | 18 | | PA | 2-0 | 33-13-18 | D03736 | 8 | | DK | | | | SP02272 | 9 | | | 050-099, 150-155, 162-165, 275-276 |
| 046 | 18 | | PA | 0-9 | 33-13-18 | D03736 | 8 | | DK | | | | SP02272 | 9 | | | 156-157, 166-199, 277-299 |
| 060 | 22 | | PA | 17-5 | 33-16-12 | D04990P | 1 | | | | | | D02772 | 1 | | | ALL |
| 061 | 20 | | PA | 2-8 | 33-16-12 | GD04458 | D.. | 2 | | | | | D02772 | 2 | | | ALL |
| 062 | 20 | | PA | 2-8 | 33-16-17 | GD04458 | D.. | 2 | | | | | D02772 | 9 | | | ALL |
| 063 | 22 | | PA | 14-8 | 33-16-17 | TB0031F | A026 | 2 | | | | | D02772 | 7 | | | ALL |
| 070 | 22 | | PQ | 17-4 | 33-16-12 | D04990P | 2 | | | | | | D02774 | 2 | | | ALL |
| 070Z | | | CT | 0-0 | 33-16-12 | D04990P | DED | | | | | | D02774 | DED | | | ALL |
| 071 | 22 | | PQ | 17-6 | 33-16-12 | D05282P | 1 | | | | | | D02774 | 1 | | | ALL |
| 071Z | | | CU | 0-0 | 33-16-12 | D05282P | DED | | | | | | D02774 | DED | | | ALL |
| 091 | 18 | | PA | 1-0 | 33-13-18 | D03734 | 8 | | DK | | | | SP02290 | 9 | | | ALL |
| 092 | 18 | | PA | 1-0 | 33-13-18 | D03756 | 8 | | DK | | | | SP02284 | 9 | | | 050-099, 150-155, 162-165, 275-276 |
| 093 | 22 | | PA | 14-2 | SPARE | D04990P | 19 | | | | | | D05395J | 19 | | | ALL |
| 094 | 22 | | PA | 14-2 | 29-21-32 | D04990P | 20 | | | | | | D05395J | 20 | | | ALL |
| 095 | 22 | | PA | 14-2 | SPARE | D04990P | 21 | | | | | | D05395J | 21 | | | ALL |
| 096 | 22 | | PA | 14-2 | 29-21-32 | D04990P | 22 | | | | | | D05395J | 22 | | | ALL |
| 097 | 22 | | PA | 14-2 | 29-21-32 | D04990P | 23 | | | | | | D05395J | 23 | | | ALL |
| 099 | 22 | | PA | 14-7 | 21-33-11 | D04560J | 12 | | | | | | D05282P | 12 | | | ALL |
| 100 | 22 | | PA | 14-2 | 29-21-32 | D04990P | 18 | | | | | | D05395J | 18 | | | ALL |
| 101 | 22 | | PA | 14-2 | 29-21-32 | D04990P | 17 | | | | | | D05395J | 17 | | | ALL |
| 102 | 18 | | PA | 0-6 | 33-13-18 | D10204 | 2 | | DK | | | | SM00012 | 9 | | | ALL |
| 104 | 18 | | PA | 2-0 | 33-13-18 | D10204 | 9 | | DK | | | | SP02280 | 9 | | | 050-099, 150-155, 162-165, 275-276 |
| 104 | 18 | | PA | 0-9 | 33-13-18 | D10204 | 9 | | DK | | | | SP02280 | 9 | | | 156-157, 166-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0630

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|---------|------|--------|---------------------------------------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0632 | 286T0632 | | | FWD FLDK INSTR PNL,UTIL LTS,WARN & CAUTION LTS (continued) | | | | | | | | | | | | |
| 105 | 22 | | PA | | 18-7 | 33-13-18 | D10204 | | | | SM00001 | | | 9 | ALL | |
| 106 | 16 | | PA | | 1-8 | 33-13-18 | D10204 | | | | GD04452 | A.. | | 2 | ALL | |
| 107 | 20 | | PA | | 2-0 | 33-13-18 | D10204 | | | | GD04452 | S.. | | 2 | ALL | |
| 109 | 18 | | PA | | 1-0 | 33-13-18 | D03756 | | | | SP02286 | | | 9 | 050-099, 150-155, 162-165, 275-276 | |
| 110 | 18 | | PA | | 1-0 | 33-13-18 | D03734 | | | | SP02292 | | | 9 | ALL | |
| 112 | 22 | | PA | | 9-8 | 33-16-12 | D06164P | | | | D02772 | | | 3 | ALL | |
| 113 | 22 | | PA | | 12-10 | 33-16-12 | D06164P | | | | D05395J | | | 3 | ALL | |
| 116 | 22 | | PA | | 12-10 | 33-16-12 | D06164P | | | | D05395J | | | 6 | ALL | |
| 117 | 22 | | PA | | 13-7 | 33-16-12 | D06164P | | | | TB0031H | | | 6 | 2 | ALL |
| 120 | 22 | | PA | | 9-8 | 33-16-22 | D06164P | | | | D02772 | | | 4 | ALL | |
| 125 | 24 | | PK | | 12-10 | 33-16-11 | D05395J | | | | D06164P | | | 15 | ALL | |
| 126 | 24 | | PK | | 12-10 | 33-16-11 | D05395J | | | | D06164P | | | 16 | ALL | |
| 127 | 22 | | PA | | 9-8 | 33-16-17 | D06164P | | | | D02772 | | | 8 | ALL | |
| 130 | 22 | | PA | | 9-8 | 33-16-21 | D06164P | | | 20 | D02772 | | | 6 | ALL | |
| 131 | 18 | | PA | | 0-9 | 33-13-18 | SP04098 | | | 9 | GD04456 | A.. | | 2 | 156-157, 166-199, 277-299 | |
| 132 | 18 | | PA | | 0-9 | 33-13-18 | SP04096 | | | 9 | GD04456 | A.. | | 2 | 156-157, 166-199, 277-299 | |
| 134 | 18 | | PA | | 0-9 | 33-13-18 | SP05004 | | | 9 | GD04452 | A.. | | 2 | 156-157, 166-199, 277-299 | |
| 135B | 12 | | PB | GA | 12-3 | 33-13-18 | SP05000 | | | 9 | SM00024 | | | 9 | 156-157, 166-199, 277-299 | |
| 135R | 12 | | PB | GA | 0-0 | 33-13-18 | SP02276 | | | 9 | SM00162 | | | 9 | 156-157, 166-199, 277-299 | |
| 136B | 18 | | PB | GL | 0-0 | 33-13-18 | SP05008 | | | 9 | GD04370 | A.. | E | | 156-157, 166-199, 277-299 | |
| 136R | 18 | | PB | GL | 1-0 | 33-13-18 | D03756 | | | 8 | DK | SP02284 | | | 9 | 156-157, 166-199, 277-299 |
| 137 | 16 | | PA | | 0-6 | 33-13-18 | D06166P | | | 18 | FL | SM00024 | | | 9 | 156-157, 166-199, 277-299 |
| 138B | 18 | | PB | GM | 0-0 | 33-13-18 | SP05010 | | | 9 | GD04370 | A.. | E | | 156-157, 166-199, 277-299 | |
| 138R | 18 | | PB | GM | 1-0 | 33-13-18 | D03756 | | | 9 | DK | SP02286 | | | 9 | 156-157, 166-199, 277-299 |
| 140 | 24 | | PK | | 9-8 | 33-16-11 | D02772 | | | 5 | D06164P | | | 30 | ALL | |
| 152 | 22 | | PQ | GB | 9-9 | 33-16-12 | D06166P | | | 2 | D02774 | | | 3 | ALL | |
| 152Z | | | | GB | 0-0 | 33-16-12 | D06166P | | | DED | D02774 | | | DED | ALL | |
| 153 | 22 | | PQ | GC | 13-1 | 33-16-12 | D06166P | | | 3 | D04560J | | | 3 | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0630
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|---------|-------------|------|---------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0632 | 286T0632 | | | FWD FLDK INSTR PNL,UTIL LTS,WARN & CAUTION LTS (continued) | | | | | | | | | | | |
| 153Z | | | | GC | 0-0 | 33-16-12 | D06166P | DED | | | | D04560J | DED | | ALL |
| 154 | 22 | PQ | | GD | 13-1 | 33-16-12 | D06166P | 4 | | | | D04560J | 5 | | ALL |
| 154Z | | | | GD | 0-0 | 33-16-12 | D06166P | DED | | | | D04560J | DED | | ALL |
| 155 | 22 | PQ | | GE | 9-9 | 33-16-12 | D06166P | 5 | | | | D02774 | 5 | | ALL |
| 155Z | | | | GE | 0-0 | 33-16-12 | D06166P | DED | | | | D02774 | DED | | ALL |
| 156 | 22 | PQ | | GF | 13-1 | 33-16-12 | D06166P | 6 | | | | D04560J | 6 | | ALL |
| 156Z | | | | GF | 0-0 | 33-16-12 | D06166P | DED | | | | D04560J | DED | | ALL |
| 157 | 22 | PQ | | GG | 13-8 | 33-16-12 | D06166P | 7 | | | | TB0031H | 8 | 2 | ALL |
| 157Z | | | | GG | 0-0 | 33-16-12 | D06166P | DED | | | | TB0031H | DED | | ALL |
| 158 | 22 | PQ | | GH | 13-1 | 33-16-12 | D06166P | 8 | | | | D04560J | 8 | | ALL |
| 158Z | | | | GH | 0-0 | 33-16-12 | D06166P | DED | | | | D04560J | DED | | ALL |
| 160 | 22 | PQ | | GJ | 9-9 | 33-16-22 | D06166P | 10 | | | | D02774 | 4 | | ALL |
| 160Z | | | | GJ | 0-0 | 33-16-22 | D06166P | DED | | | | D02774 | DED | | ALL |
| 161 | 22 | PQ | | GK | 9-9 | 33-16-22 | D06166P | 11 | | | | D02774 | 6 | | ALL |
| 161Z | | | | GK | 0-0 | 33-16-22 | D06166P | DED | | | | D02774 | DED | | ALL |
| 162 | 14 | PA | | | 12-3 | 33-13-18 | SP02276 | | 9 | | | SM00162 | | 9 | 050-099, 150-155, 162-165, 275-276 |
| 166 | 16 | PA | | | 0-6 | 33-13-18 | D06166P | 16 | FL | | | SM00162 | | 9 | ALL |
| 168 | 24 | PK | | | 12-11 | 33-13-18 | D05395J | 8 | | | | D06166P | 14 | | ALL |
| 172 | 16 | PA | | | 0-6 | 33-13-18 | D06166P | 12 | FL | | | SM00014 | | 9 | ALL |
| 174 | 14 | PA | | | 11-9 | 33-13-18 | SM00014 | | 9 | | | SM00012 | | 9 | ALL |
| 201B | 24 | PL | BA | | 15-3 | 21-61-11 | D05282P | 2 | | | | D03830 | 1 | | ALL |
| 201R | 24 | PL | BA | | 0-0 | 21-61-11 | D05282P | 3 | | | | D03830 | 2 | | ALL |
| 202B | 24 | PL | BB | | 27-3 | 21-61-11 | D05282P | 4 | | | | D03828 | 1 | | ALL |
| 202R | 24 | PL | BB | | 0-0 | 21-61-11 | D05282P | 5 | | | | D03828 | 2 | | ALL |
| 303B | 24 | PM | CC | | 16-11 | 33-13-18 | SM00009 | | 9 | | | D05282P | 19 | | ALL |
| 303R | 24 | PM | CC | | 0-0 | 33-13-18 | SM00010 | | 9 | | | D05282P | 18 | | ALL |
| 303Y | 24 | PM | CC | | 0-0 | 33-13-18 | SM00011 | | 9 | | | D05282P | 20 | | ALL |
| 304B | 24 | PM | CD | | 8-11 | 33-13-18 | SM00009 | | 9 | | | D03734 | 5 | | ALL |
| 304R | 24 | PM | CD | | 0-0 | 33-13-18 | SM00010 | | 9 | | | D03734 | 6 | | ALL |
| 304Y | 24 | PM | CD | | 0-0 | 33-13-18 | SM00011 | | 9 | | | D03734 | 1 | | ALL |
| 305B | 24 | PM | CE | | 3-3 | 33-13-18 | SM00009 | | 9 | | | D03736 | 5 | | ALL |
| 305R | 24 | PM | CE | | 0-0 | 33-13-18 | SM00010 | | 9 | | | D03736 | 6 | | ALL |
| 305Y | 24 | PM | CE | | 0-0 | 33-13-18 | SM00011 | | 9 | | | D03736 | 1 | | ALL |
| 306B | 24 | PM | CF | | 8-10 | 33-13-18 | SM00009 | | 9 | | | D03756 | 5 | | ALL |
| 306R | 24 | PM | CF | | 0-0 | 33-13-18 | SM00010 | | 9 | | | D03756 | 6 | | ALL |
| 306Y | 24 | PM | CF | | 0-0 | 33-13-18 | SM00011 | | 9 | | | D03756 | 1 | | ALL |
| 307B | 24 | PM | CG | | 3-6 | 33-13-18 | D10204 | | 5 | | | SM00009 | | 9 | ALL |
| 307R | 24 | PM | CG | | 0-0 | 33-13-18 | D10204 | | 6 | | | SM00010 | | 9 | ALL |

WIRE LIST

D280T132

91-21-11

Section W0630

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0632 | 286T0632 | | | FWD FLDK INSTR PNL,UTIL LTS,WARN & CAUTION LTS (continued) | | | | | | | | | | | |
| 307Y | 24 | PM | CG | 0-0 | 33-13-18 | D10204 | | 1 | | SM00011 | | 9 | | ALL | |
| 520 | 22 | PA | | 14-7 | 30-33-11 | D04560J | | 13 | | D05282P | | 13 | | ALL | |
| 801 | 20 | PA | | 14-7 | SPARE | D04560J | | 22 | | D05282P | | 35 | | ALL | |
| 802 | 22 | PA | | 14-7 | SPARE | D04560J | | 23 | | D05282P | | 36 | | ALL | |
| 803 | 24 | PK | | 14-7 | SPARE | D04560J | | 24 | | D05282P | | 37 | | ALL | |
| 804 | 24 | PK | | 14-2 | 32-61-14 | D05395J | | 35 | | D04990P | | 28 | | ALL | |
| 805 | 24 | PK | | 14-2 | 32-61-14 | D05395J | | 36 | | D04990P | | 29 | | ALL | |
| 806 | 24 | PK | | 14-2 | 32-61-14 | D05395J | | 37 | | D04990P | | 30 | | ALL | |
| B-A | | | | 0-0 | 33-14-31 | L00412 | | WHT | | TB5100 | | = P | E | ALL | |
| B-B | | | | 0-0 | 33-14-31 | L00412 | | SHLD | | TB5100 | | = G | E | ALL | |
| C-A | | | | 0-0 | 33-14-31 | L00034 | | WHT | | TB5102 | | = P | E | ALL | |
| C-B | | | | 0-0 | 33-14-31 | L00034 | | SHLD | | TB5102 | | = G | E | ALL | |
| D-A | | | | 0-0 | 33-14-31 | L00037 | | WHT | | TB5104 | | = P | E | ALL | |
| D-B | | | | 0-0 | 33-14-31 | L00037 | | SHLD | | TB5104 | | = G | E | ALL | |
| W0633 | 286T0633 | | | HF L,SHELF TO TAIL DISC | | | | | | | | | | | |
| 001 | 24 | PK | | 134-0 | 23-11-11 | D04787J | | 1 | | D04825P | | 1 | | 050-099 | |
| 001 | 24 | PK | | 155-0 | 23-11-11 | D04787J | | 1 | | D04825P | | 1 | | 150-199, 275-299 | |
| 002 | 24 | PK | | 134-0 | 23-11-11 | D04787J | | 2 | | D04825P | | 2 | | 050-099 | |
| 002 | 24 | PK | | 155-0 | 23-11-11 | D04787J | | 2 | | D04825P | | 2 | | 150-199, 275-299 | |
| 003 | 24 | PK | | 134-0 | 23-11-11 | D04787J | | 3 | | D04825P | | 3 | | 050-099 | |
| 003 | 24 | PK | | 155-0 | 23-11-11 | D04787J | | 3 | | D04825P | | 3 | | 150-199, 275-299 | |
| 004 | 24 | PK | | 134-0 | 23-11-11 | D04787J | | 4 | | D04825P | | 4 | | 050-099 | |
| 004 | 24 | PK | | 155-0 | 23-11-11 | D04787J | | 4 | | D04825P | | 4 | | 150-199, 275-299 | |
| 005 | 24 | PK | | 134-0 | 23-11-11 | D04787J | | 5 | | D04825P | | 5 | | 050-099 | |
| 005 | 24 | PK | | 155-0 | 23-11-11 | D04787J | | 5 | | D04825P | | 5 | | 150-199, 275-299 | |
| 006 | 20 | PA | | 134-0 | 23-11-11 | D04787J | | 6 | | D04825P | | 6 | | 050-099 | |
| 006 | 20 | PA | | 155-0 | 23-11-11 | D04787J | | 6 | | D04825P | | 6 | | 150-199, 275-299 | |
| W0634 | 286T0634 | | | FWD FLDK INSTR PNL LTS,WARN & CAUTION LTS | | | | | | | | | | | |
| 007 | 24 | PK | | 13-2 | 33-13-11 | D05784P | | 8 | | D05347J | | 8 | | ALL | |
| 013R | 22 | PH | | 13-2 | 26-11-11 | D05784P | | 16 | | D05347J | | 16 | | ALL | |
| 016 | 16 | PA | | 17-4 | 33-11-14 | D04986P | | 16 | | L00038 | | = P | C | ALL | |
| 018 | 16 | PA | | 17-1 | 33-11-14 | D04986P | | 18 | | L00039 | | = P | C | ALL | |
| 019 | 24 | PK | | 13-2 | 31-25-11 | D05784P | | 15 | | D05347J | | 17 | | ALL | |
| 020 | 24 | PK | | 13-5 | 31-25-11 | D05792P | | 15 | | D04556J | | 15 | | ALL | |
| 021 | 22 | PA | | 13-5 | 32-41-11 | D05792P | | 13 | | D04556J | | 13 | | ALL | |
| 032 | 16 | PA | | 9-6 | 33-11-14 | L00038 | | = G | C | GD00112 | | A.. | 2 | ALL | |
| 033 | 16 | PA | | 3-11 | 33-11-14 | L00039 | | = G | C | GD00112 | | A.. | 2 | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0630

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0634 | 286T0634 | | | FWD FLDK INSTR PNL LTS,WARN & CAUTION LTS (continued) | | | | | | | | | | | | | |
| 035 | 24 | | PK | 13-5 | 33-11-13 | D04556J | | 11 | | | | | D05792P | 11 | | | ALL |
| 041 | 24 | | PK | 12-9 | 33-11-11 | D05347J | | 1 | | | | | D06168P | 1 | | | ALL |
| 042 | 24 | | PK | 12-9 | 33-11-11 | D05347J | | 2 | | | | | D06168P | 2 | | | ALL |
| 043 | 24 | | PK | 13-2 | 33-11-11 | D04556J | | 1 | | | | | D06170P | 1 | | | ALL |
| 044 | 24 | | PK | 13-2 | 33-11-11 | D04556J | | 2 | | | | | D06170P | 2 | | | ALL |
| 050 | 22 | | PA | 12-8 | 34-12-61 | D06168P | | 9 | | | | | D04556J | 12 | | | ALL |
| 057 | 22 | | PA | 17-6 | 33-51-11 | D05784P | | 17 | | | | | M00744 | 2 | | C | ALL |
| 058 | 22 | | PA | 17-6 | 33-51-11 | D05784P | | 18 | | | | | M00744 | 3 | | C | ALL |
| 059 | 22 | | PA | 17-6 | 33-51-11 | D05784P | | 19 | | | | | M00744 | 4 | | C | ALL |
| 060 | 20 | | PA | 7-3 | 33-51-11 | M00744 | | 5 | | C | | | GD00434 | D.. | | 2 | ALL |
| 080 | 22 | | PA | 15-8 | 33-16-12 | D05784P | | 1 | | | | | D02780 | 1 | | | ALL |
| 081 | 20 | | PA | 2-9 | 33-16-12 | GD04458 | | D.. | | 2 | | | D02780 | 2 | | | ALL |
| 082 | 20 | | PA | 2-8 | 33-16-17 | GD04458 | | D.. | | 2 | | | D02782 | 9 | | | ALL |
| 083 | 22 | | PA | 15-0 | 33-16-17 | TB0031F | | A025 | | 2 | | | D02782 | 7 | | | ALL |
| 090 | 22 | | PQ | 15-7 | 33-16-12 | D05784P | | 2 | | | | | D02782 | 2 | | | ALL |
| 090Z | | | DO | 0-0 | 33-16-12 | D05784P | | DED | | | | | D02782 | DED | | | ALL |
| 091 | 22 | | PQ | 15-10 | 33-16-12 | D05792P | | 1 | | | | | D02782 | 1 | | | ALL |
| 091Z | | | DP | 0-0 | 33-16-12 | D05792P | | DED | | | | | D02782 | DED | | | ALL |
| 120 | 22 | | PA | 10-0 | 33-16-22 | D06168P | | 10 | | | | | D02780 | 4 | | | ALL |
| 121 | 22 | | PA | 10-0 | 33-16-22 | D06168P | | 11 | | | | | D02780 | 10 | | | ALL |
| 122 | 22 | | PA | 10-0 | 33-16-22 | D06168P | | 12 | | | | | D02780 | 11 | | | ALL |
| 125 | 24 | | PK | 12-9 | 33-16-11 | D05347J | | 10 | | | | | D06168P | 15 | | | ALL |
| 126 | 24 | | PK | 12-9 | 33-16-11 | D05347J | | 11 | | | | | D06168P | 16 | | | ALL |
| 127 | 22 | | PA | 9-11 | 33-16-17 | D06168P | | 17 | | | | | D02782 | 8 | | | ALL |
| 130 | 22 | | PA | 10-0 | 33-16-21 | D06168P | | 20 | | | | | D02780 | 6 | | | ALL |
| 131 | 22 | | PA | 10-0 | 33-16-12 | D06168P | | 21 | | | | | D02780 | 3 | | | ALL |
| 132 | 22 | | PA | 10-6 | 33-16-12 | SM00001 | | | | S | | | D05347J | 20 | | | ALL |
| 133 | 22 | | PA | 12-9 | 33-16-12 | D06168P | | 23 | | | | | D05347J | 21 | | | ALL |
| 134 | 22 | | PA | 14-5 | 33-16-12 | D06168P | | 24 | | | | | TB0031G | 10 | | 2 | ALL |
| 135 | 22 | | PA | 10-6 | 33-16-12 | SM00002 | | | | S | | | D05347J | 22 | | | ALL |
| 136 | 22 | | PA | 14-5 | 33-16-12 | D06168P | | 26 | | | | | TB0031H | 11 | | 2 | ALL |
| 137 | 22 | | PA | 14-5 | 33-16-12 | D06168P | | 27 | | | | | TB0031H | 13 | | 2 | ALL |
| 138 | 22 | | PA | 14-5 | 33-16-12 | D06168P | | 28 | | | | | TB0031G | 15 | | 2 | ALL |
| 140 | 24 | | PK | 10-0 | 33-16-11 | D02780 | | 5 | | | | | D06168P | 30 | | | ALL |
| 141 | 24 | | PK | 10-0 | 33-16-11 | D02780 | | 12 | | | | | D06168P | 31 | | | ALL |
| 142 | 22 | | PA | 2-10 | 33-16-12 | SM00001 | | | | S | | | D06168P | 22 | | | ALL |
| 143 | 22 | | PA | 14-9 | 33-16-18 | SM00001 | | | | S | | | TB0031Y | A004 | | BJ | ALL |
| 144 | 22 | | PA | 14-9 | 33-16-18 | SM00002 | | | | S | | | TB0031Y | C004 | | BJ | ALL |
| 145 | 22 | | PA | 2-10 | 33-16-12 | SM00002 | | | | S | | | D06168P | 25 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0630

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0634 | 286T0634 | | | FWD FLDK INSTR PNL LTS,WARN & CAUTION LTS (continued) | | | | | | | | | | | |
| 160 | 22 | PQ | GJ | 10-2 | 33-16-22 | D06170P | 10 | | | D02782 | 4 | | | ALL | |
| 160Z | | | GJ | 0-0 | 33-16-22 | D06170P | DED | | | D02782 | DED | | | ALL | |
| 171 | 22 | PQ | GU | 10-2 | 33-16-12 | D06170P | 21 | | | D02782 | 3 | | | ALL | |
| 171Z | | | GU | 0-0 | 33-16-12 | D06170P | DED | | | D02782 | DED | | | ALL | |
| 172 | 22 | PQ | GV | 14-8 | 33-16-12 | D06170P | 22 | | | TB0031H | 16 | 2 | | ALL | |
| 172Z | | | GV | 0-0 | 33-16-12 | D06170P | DED | | | TB0031H | DED | | | ALL | |
| 173 | 22 | PQ | GW | 13-2 | 33-16-12 | D06170P | 23 | | | D04556J | 20 | | | ALL | |
| 173Z | | | GW | 0-0 | 33-16-12 | D06170P | DED | | | D04556J | DED | | | ALL | |
| 174 | 22 | PQ | GX | 10-2 | 33-16-12 | D06170P | 24 | | | D02782 | 10 | | | ALL | |
| 174Z | | | GX | 0-0 | 33-16-12 | D06170P | DED | | | D02782 | DED | | | ALL | |
| 175 | 22 | PQ | GY | 13-2 | 33-16-12 | D06170P | 25 | | | D04556J | 21 | | | ALL | |
| 175Z | | | GY | 0-0 | 33-16-12 | D06170P | DED | | | D04556J | DED | | | ALL | |
| 176 | 22 | PQ | HA | 10-2 | 33-16-12 | D06170P | 26 | | | D02782 | 5 | | | ALL | |
| 176Z | | | HA | 0-0 | 33-16-12 | D06170P | DED | | | D02782 | DED | | | ALL | |
| 177 | 22 | PQ | HB | 14-8 | 33-16-12 | D06170P | 27 | | | TB0031H | 18 | 2 | | ALL | |
| 177Z | | | HB | 0-0 | 33-16-12 | D06170P | DED | | | TB0031H | DED | | | ALL | |
| 178 | 22 | PQ | HC | 13-2 | 33-16-12 | D06170P | 28 | | | D04556J | 22 | | | ALL | |
| 178Z | | | HC | 0-0 | 33-16-12 | D06170P | DED | | | D04556J | DED | | | ALL | |
| 188 | 16 | PA | | 12-9 | 33-13-18 | D05347J | 27 | | | D06168P | 38 | FL | | ALL | |
| 201B | 24 | PW | BA | 12-9 | 33-11-11 | D05347J | 3 | | | D06168P | 3 | | | ALL | |
| 201R | 24 | PW | BA | 0-0 | 33-11-11 | D05347J | 4 | | | D06168P | 4 | | | ALL | |
| 201Z | | | BA | 0-0 | 33-11-11 | D05347J | | | FA | D06168P | | | FC | ALL | |
| 202B | 24 | PW | BB | 13-2 | 33-11-11 | D04556J | 3 | | | D06170P | 3 | | | ALL | |
| 202R | 24 | PW | BB | 0-0 | 33-11-11 | D04556J | 4 | | | D06170P | 4 | | | ALL | |
| 202Z | | | BB | 0-0 | 33-11-11 | D04556J | | | FB | D06170P | | | FD | ALL | |
| 301B | 24 | PX | CA | 12-9 | 33-11-11 | D05347J | 5 | | | D06168P | 5 | | | ALL | |
| 301R | 24 | PX | CA | 0-0 | 33-11-11 | D05347J | 6 | | | D06168P | 6 | | | ALL | |
| 301Y | 24 | PX | CA | 0-0 | 33-11-11 | D05347J | 7 | | | D06168P | 7 | | | ALL | |
| 301Z | | | CA | 0-0 | 33-11-11 | D05347J | | | FA | D06168P | | | FC | ALL | |
| 302B | 24 | PX | MB | 13-2 | 33-11-11 | D04556J | 5 | | | D06170P | 5 | | | ALL | |
| 302R | 24 | PX | MB | 0-0 | 33-11-11 | D04556J | 6 | | | D06170P | 6 | | | ALL | |
| 302Y | 24 | PX | MB | 0-0 | 33-11-11 | D04556J | 7 | | | D06170P | 7 | | | ALL | |
| 302Z | | | MB | 0-0 | 33-11-11 | D04556J | | | FB | D06170P | | | FD | ALL | |
| 303B | 24 | PM | CC | 13-5 | 33-11-13 | D04556J | 8 | | | D05792P | 8 | | | ALL | |
| 303R | 24 | PM | CC | 0-0 | 33-11-13 | D04556J | 9 | | | D05792P | 9 | | | ALL | |
| 303Y | 24 | PM | CC | 0-0 | 33-11-13 | D04556J | 10 | | | D05792P | 10 | | | ALL | |
| 521 | 24 | PK | | 13-2 | 73-21-14 | D05347J | 14 | | | D05784P | 14 | | | ALL | |
| 530 | 12 | PA | | 13-9 | 32-35-11 | D04986P | 20 | | | D05347J | 19 | | | ALL | |
| 532 | 18 | PA | | 28-4 | 32-35-11 | D05347J | 23 | | | D06198P | 2 | | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0630
Page 8
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0634 | 286T0634 | | | FWD FLDK INSTR PNL LTS,WARN & CAUTION LTS (continued) | | | | | | | | | | | | | |
| 533 | 12 | PA | | 28-4 | 32-35-11 | D05347J | | 15 | | | | | D06198P | 1 | | | ALL |
| 540R | 22 | PH | | 13-2 | 26-17-11 | D05347J | | 9 | | | | | D05784P | 9 | | | ALL |
| 801 | 22 | PA | | 13-5 | SPARE | D04556J | | 18 | | | | | D05792P | 28 | | | ALL |
| 802 | 22 | PA | | 13-5 | SPARE | D04556J | | 19 | | | | | D05792P | 29 | | | ALL |
| 803 | 22 | PA | | 2-6 | SPARE | D04986P | | 25 | | | | | D05792P | 30 | | | ALL |
| 804 | 22 | PA | | 13-2 | SPARE | D05347J | | 12 | | | | | D05784P | 29 | | | ALL |
| 805 | 22 | PA | | 13-2 | SPARE | D05347J | | 13 | | | | | D05784P | 30 | | | ALL |
| FRA | | | | 0-0 | 33-11-11 | D05347J | | | | FA | | | D05347J | 24 | | | ALL |
| FRB | | | | 0-0 | 33-11-11 | D04556J | | | | FB | | | D04556J | 23 | | | ALL |
| FRC | | | | 0-0 | 33-11-11 | D06168P | | | | FC | | | D06168P | 8 | | | ALL |
| FRD | | | | 0-0 | 33-11-11 | D06170P | | | | FD | | | D06170P | 8 | | | ALL |
| W0635 | 286T0635 | | | HF R,SHELF TO TAIL DISC | | | | | | | | | | | | | |
| 001 | 24 | PK | | 128-0 | 23-11-21 | D04789J | | 1 | | | | | D04827P | 1 | | | 050-099 |
| 001 | 24 | PK | | 149-0 | 23-11-21 | D04789J | | 1 | | | | | D04827P | 1 | | | 150-199, 275-299 |
| 002 | 24 | PK | | 128-0 | 23-11-21 | D04789J | | 2 | | | | | D04827P | 2 | | | 050-099 |
| 002 | 24 | PK | | 149-0 | 23-11-21 | D04789J | | 2 | | | | | D04827P | 2 | | | 150-199, 275-299 |
| 003 | 24 | PK | | 128-0 | 23-11-21 | D04789J | | 3 | | | | | D04827P | 3 | | | 050-099 |
| 003 | 24 | PK | | 149-0 | 23-11-21 | D04789J | | 3 | | | | | D04827P | 3 | | | 150-199, 275-299 |
| 004 | 24 | PK | | 128-0 | 23-11-21 | D04789J | | 4 | | | | | D04827P | 4 | | | 050-099 |
| 004 | 24 | PK | | 149-0 | 23-11-21 | D04789J | | 4 | | | | | D04827P | 4 | | | 150-199, 275-299 |
| 005 | 24 | PK | | 128-0 | 23-11-21 | D04789J | | 5 | | | | | D04827P | 5 | | | 050-099 |
| 005 | 24 | PK | | 149-0 | 23-11-21 | D04789J | | 5 | | | | | D04827P | 5 | | | 150-199, 275-299 |
| 006 | 20 | PA | | 128-0 | 23-11-21 | D04789J | | 6 | | | | | D04827P | 6 | | | 050-099 |
| 006 | 20 | PA | | 149-0 | 23-11-21 | D04789J | | 6 | | | | | D04827P | 6 | | | 150-199, 275-299 |
| W0636 | 286T0636 | | | FLT INST PNL,STBY MAGN COMPASS-PNL LT | | | | | | | | | | | | | |
| 001 | 18 | PQ | A | 3-0 | 33-13-11 | D06366P | | = 1 | | | | | D00642 | = A1 | | | ALL |
| 001Z | | | A | 0-0 | 33-13-11 | D06368J | | = 1 | | | | | D00642 | = C1 | | | ALL |
| W0638 | 286T0638 | | | FWD FLDK INSTR R PNL LTS,WARN & CAUTION LTS | | | | | | | | | | | | | |
| 001 | 20 | PA | | 14-5 | 33-42-11 | D05399J | | 11 | | | | | D04994P | 11 | | | ALL |
| 002 | 24 | PK | | 27-6 | 21-61-11 | D04994P | | 12 | | | | | D03838 | 1 | | | ALL |
| 003 | 20 | PA | | 3-10 | 21-61-11 | D03838 | | 2 | | | | | GD01742 | D.. | E | | ALL |
| 004 | 20 | PA | | 1-0 | 21-65-11 | D02608 | | B | | | | | SM00004 | | S | | ALL |
| 005 | 20 | PA | | 3-10 | 21-65-11 | SM00004 | | | | S | | | GD01742 | D.. | E | | ALL |
| 013 | 16 | PA | | 14-4 | 33-11-14 | L00047 | | = P | C | | | | D04994P | 20 | FL | | ALL |
| 014 | 16 | PA | | 7-8 | 33-11-14 | L00047 | | = G | C | | | | GD00112 | A.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0630

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0638 | 286T0638 | | | FWD FLDK INSTR R PNL LTS,WARN & CAUTION LTS (continued) | | | | | | | | | | | |
| 015 | 22 | | PA | | 14-5 | 33-13-13 | D04994P | | 13 | | D05399J | | 13 | | ALL |
| 016 | 24 | | PK | | 14-5 | 33-13-17 | D04994P | | 14 | | D05399J | | 14 | | ALL |
| 049 | 22 | | PA | | 12-4 | 34-12-62 | D06172P | | 8 | | D05393J | | 8 | | ALL |
| 060 | 22 | | PA | | 16-5 | 33-16-12 | D04994P | | 1 | | D02776 | | 1 | | ALL |
| 061 | 20 | | PA | | 2-5 | 33-16-12 | GD04458 | | D.. | 2 | D02776 | | 2 | | ALL |
| 062 | 20 | | PA | | 2-5 | 33-16-17 | GD04458 | | D.. | 2 | D02778 | | 9 | | ALL |
| 063 | 22 | | PA | | 14-11 | 33-16-17 | TB0031F | | C025 | 2 | D02778 | | 7 | | ALL |
| 070 | 22 | | PQ | CT | 16-5 | 33-16-12 | D04994P | | | 2 | D02778 | | 2 | | ALL |
| 070Z | | | | CT | 0-0 | 33-16-12 | D04994P | | | DED | D02778 | | DED | | ALL |
| 071 | 22 | | PQ | CU | 16-5 | 33-16-12 | D04994P | | | 6 | D02778 | | 1 | | ALL |
| 071Z | | | | CU | 0-0 | 33-16-12 | D04994P | | | DED | D02778 | | DED | | ALL |
| 100 | 24 | | PK | | 14-5 | 33-14-11 | D05399J | | | 18 | D04994P | | 18 | | ALL |
| 101 | 24 | | PK | | 26-10 | 33-14-11 | D05399J | | | 19 | L00031 | | =P | C | ALL |
| 102 | 20 | | PA | | 6-5 | 33-14-11 | GD00112 | | A.. | 2 | L00031 | | =G | C | ALL |
| 103 | 24 | | PK | | 27-4 | 33-14-11 | D05399J | | | 20 | L00030 | | =P | C | ALL |
| 104 | 20 | | PA | | 12-1 | 33-14-11 | GD00112 | | A.. | 2 | L00030 | | =G | C | ALL |
| 112 | 22 | | PA | | 14-3 | 33-16-12 | D06172P | | | 2 | D02776 | | 3 | | ALL |
| 113 | 22 | | PA | | 12-2 | 33-16-12 | D06172P | | | 3 | D05399J | | 3 | | ALL |
| 115 | 22 | | PA | | 12-2 | 33-16-12 | D06172P | | | 5 | D05399J | | 5 | | ALL |
| 116 | 22 | | PA | | 9-2 | 33-16-12 | D06172P | | | 6 | SP00273 | | | S | ALL |
| 120 | 22 | | PA | | 14-3 | 33-16-22 | D06172P | | | 10 | D02776 | | 4 | | ALL |
| 127 | 22 | | PA | | 14-2 | 33-16-17 | D06172P | | | 17 | D02778 | | 8 | | ALL |
| 130 | 22 | | PA | | 14-3 | 33-16-21 | D06172P | | | 20 | D02776 | | 6 | | ALL |
| 140 | 24 | | PK | | 14-3 | 33-16-11 | D06172P | | | 30 | D02776 | | 5 | | ALL |
| 151 | 22 | | PQ | GA | 14-3 | 33-16-12 | D06174P | | | 1 | D02778 | | 3 | | ALL |
| 151Z | | | | GA | 0-0 | 33-16-12 | D06174P | | | DED | D02778 | | DED | | ALL |
| 152 | 22 | | PQ | GB | 12-5 | 33-16-12 | D06174P | | | 2 | D05393J | | 2 | | ALL |
| 152Z | | | | GB | 0-0 | 33-16-12 | D06174P | | | DED | D05393J | | DED | | ALL |
| 154 | 22 | | PQ | GD | 14-3 | 33-16-12 | D06174P | | | 4 | D02778 | | 5 | | ALL |
| 154Z | | | | GD | 0-0 | 33-16-12 | D06174P | | | DED | D02778 | | DED | | ALL |
| 155 | 22 | | PQ | GE | 12-5 | 33-16-12 | D06174P | | | 5 | D05393J | | 5 | | ALL |
| 155Z | | | | GE | 0-0 | 33-16-12 | D06174P | | | DED | D05393J | | DED | | ALL |
| 156 | 22 | | PQ | GF | 9-3 | 33-16-12 | D06174P | | | 6 | SP00271 | | | S | ALL |
| 156Z | | | | GF | 0-0 | 33-16-12 | D06174P | | | DED | SP00271 | | DED | | ALL |
| 157 | 22 | | PQ | GG | 12-5 | 33-16-12 | D06174P | | | 7 | D05393J | | 7 | | ALL |
| 157Z | | | | GG | 0-0 | 33-16-12 | D06174P | | | DED | D05393J | | DED | | ALL |
| 158 | 22 | | PQ | GH | 18-6 | 33-16-12 | D06174P | | | 8 | TB0031G | | 27 | 2 | 150-154, 275-278 |
| 158Z | | | | GH | 0-0 | 33-16-12 | D06174P | | | DED | TB0031G | | DED | | 150-154, 275-278 |
| 160 | 22 | | PQ | GJ | 14-3 | 33-16-22 | D06174P | | | 10 | D02778 | | 4 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0630

Page 10

Mar 14/2007



| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0638 | 286T0638 | | | FWD FLDK INSTR R PNL LTS,WARN & CAUTION LTS (continued) | | | | | | | | | | | |
| 160Z | | | | GJ | 0-0 | 33-16-22 | D06174P | | DED | | D02778 | | DED | | ALL |
| 201B | 20 | PB | BA | | 27-6 | 21-65-11 | D04994P | | 7 | | D02608 | | A | | ALL |
| 201R | 20 | PB | BA | | 0-0 | 21-65-11 | D04994P | | 8 | | SM00004 | | | S | ALL |
| 302B | 24 | PM | CB | | 14-5 | 33-13-17 | D05399J | | 15 | | D04994P | | 15 | | ALL |
| 302R | 24 | PM | CB | | 0-0 | 33-13-17 | D05399J | | 16 | | D04994P | | 16 | | ALL |
| 302Y | 24 | PM | CB | | 0-0 | 33-13-17 | D05399J | | 17 | | D04994P | | 17 | | ALL |
| 801 | 22 | PA | | | 14-5 | SPARE | D05399J | | 29 | | D04994P | | 28 | | ALL |
| 802 | 22 | PA | | | 14-5 | SPARE | D05399J | | 30 | | D04994P | | 29 | | ALL |
| 803 | 22 | PA | | | 14-6 | SPARE | D05393J | | 10 | | D04994P | | 30 | | ALL |
| 804 | 22 | PA | | | 14-6 | SPARE | D05393J | | 11 | | D04994P | | 31 | | ALL |
| W0639 | 286T0639 | | | E2-5 TO MID ATTENDANTS CEILING DISC. | | | | | | | | | | | |
| 401B | 24 | PY | QA | | 74-0 | 23-42-11 | D04615J | | 2 | | D04669J | | 3 | | 050-099 |
| 401B | 24 | PY | QA | | 92-0 | 23-42-11 | D04615J | | 2 | | D04669J | | 3 | | 150-199 |
| 401B | 24 | PY | QA | | 82-0 | 23-42-11 | D04615J | | 2 | | D04669J | | 3 | | 275-299 |
| 401G | 24 | PY | QA | | 0-0 | 23-42-11 | D04615J | | 4 | | D04669J | | 5 | | ALL |
| 401R | 24 | PY | QA | | 0-0 | 23-42-11 | D04615J | | 1 | | D04669J | | 1 | | ALL |
| 401Y | 24 | PY | QA | | 0-0 | 23-42-11 | D04615J | | 3 | | D04669J | | 4 | | ALL |
| 401Z | | | | QA | 0-0 | 23-42-11 | D04615J | | 5 | | D04669J | | 2 | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0640 | 286T0640 | | | CARGO COMPARTMENT FIRE EXTINGUISHING BOTTLE 1 | | | | | | | | | | | |
| 001R | 20 | | PH | | 4-0 | 26-23-11 | D01448 | | 2 | | D06880J | | 6 | | 050-099 |
| 002R | 20 | | PH | | 2-0 | 26-23-11 | D01440 | | 1 | | D06880J | | 9 | | 050-099 |
| 003R | 20 | | PH | | 2-0 | 26-23-11 | D01442 | | 1 | | D06880J | | 12 | | 050-099 |
| 004R | 20 | | PH | | 4-0 | 26-23-11 | D01448 | | 3 | | GD05830 | D.. | E | * | 050-099 |
| 005R | 20 | | PH | | 2-0 | 26-23-11 | D01440 | | 2 | | GD05830 | D.. | E | * | 050-099 |
| 006R | 20 | | PH | | 3-0 | 26-23-11 | D01442 | | 2 | | GD05830 | D.. | E | * | 050-099 |
| 007R | 20 | | PH | | 4-0 | 26-23-11 | D01448 | | 1 | | GD05832 | S.. | E | * | 050-099 |
| 008R | 20 | | PH | | 2-0 | 26-23-11 | D01440 | | 3 | | GD05832 | S.. | E | * | 050-099 |
| 009R | 20 | | PH | | 3-0 | 26-23-11 | D01442 | | 3 | | GD05832 | S.. | E | * | 050-099 |
| W0642 | 286T0642 | | | CARGO COMPARTMENT FIRE EXTINGUISHING BOTTLE 2 | | | | | | | | | | | |
| 001R | 20 | | PH | | 4-0 | 26-23-12 | D01454 | | 2 | | D06882J | | 8 | | 050-099 |
| 002R | 20 | | PH | | 2-0 | 26-23-12 | D01450 | | 1 | | D06882J | | 12 | | 050-099 |
| 003R | 20 | | PH | | 3-0 | 26-23-12 | D01452 | | 1 | | D06882J | | 15 | | 050-099 |
| 004R | 20 | | PH | | 4-0 | 26-23-12 | D01454 | | 3 | | GD05834 | D.. | E | * | 050-099 |
| 005R | 20 | | PH | | 2-0 | 26-23-12 | D01450 | | 2 | | GD05834 | D.. | E | * | 050-099 |
| 006R | 20 | | PH | | 3-0 | 26-23-12 | D01452 | | 2 | | GD05834 | D.. | E | * | 050-099 |
| 007R | 20 | | PH | | 4-0 | 26-23-12 | D01454 | | 1 | | GD05836 | S.. | E | * | 050-099 |
| 008R | 20 | | PH | | 2-0 | 26-23-12 | D01450 | | 3 | | GD05836 | S.. | E | * | 050-099 |
| 009R | 20 | | PH | | 3-0 | 26-23-12 | D01452 | | 3 | | GD05836 | S.. | E | * | 050-099 |
| W0644 | 286T0644 | | | CARGO COMPARTMENT FIRE EXTINGUISHING BOTTLE 2A | | | | | | | | | | | |
| 001R | 20 | | PH | | 3-0 | 26-23-12 | D10684 | | 2 | | D06884J | | 5 | | 050-099 |
| 002R | 20 | | PH | | 2-0 | 26-23-12 | D10680 | | 1 | | D06884J | | 8 | | 050-099 |
| 003R | 20 | | PH | | 2-0 | 26-23-12 | D10682 | | 1 | | D06884J | | 11 | | 050-099 |
| 004R | 20 | | PH | | 3-0 | 26-23-12 | D10684 | | 3 | | GD05838 | D.. | E | * | 050-099 |
| 005R | 20 | | PH | | 2-0 | 26-23-12 | D10680 | | 2 | | GD05838 | D.. | E | * | 050-099 |
| 006R | 20 | | PH | | 2-0 | 26-23-12 | D10682 | | 2 | | GD05838 | D.. | E | * | 050-099 |
| 007R | 20 | | PH | | 3-0 | 26-23-12 | D10684 | | 1 | | GD05840 | S.. | E | * | 050-099 |
| 008R | 20 | | PH | | 2-0 | 26-23-12 | D10680 | | 3 | | GD05840 | S.. | E | * | 050-099 |
| 009R | 20 | | PH | | 2-0 | 26-23-12 | D10682 | | 3 | | GD05840 | S.. | E | * | 050-099 |
| W0645 | 286T0645 | | | E2-5 TO P21 FWD LEFT ATTENDANTS PANEL | | | | | | | | | | | |
| 004 | 24 | | PK | | 35-0 | 23-31-12 | D00837 | | 4 | | D04625J | | 4 | | 050-099 |
| 005 | 20 | | PK | | 10-0 | 23-31-12 | D00837 | | 5 | | GD00017 | D.. | 2 | | 050-099 |
| 011 | 22 | | PA | | 62-0 | 23-34-11 | D00837 | | 11 | | D04625J | | 11 | | 050-099, 150-199, 275-278 |
| 011 | 22 | | PA | | 61-1 | 23-34-11 | D00837 | | 11 | | D04625J | | 11 | | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0640
Page 1
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0645 | 286T0645 | | | E2-5 TO P21 FWD LEFT ATTENDANTS PANEL (continued) | | | | | | | | | | | | | |
| 012 | 24 | | PK | 62-0 | 23-34-12 | D00837 | | 12 | | | | | D04625J | 12 | | | 050-099, 150-199, 275-278 |
| 012 | 24 | | PK | 61-1 | 23-34-12 | D00837 | | 12 | | | | | D04625J | 12 | | | 280-299 |
| 014 | 22 | | PA | 60-0 | 23-34-11 | D00837 | | 14 | | | | | SM00007 | | S | | ALL |
| 017 | 24 | | PK | 60-0 | 23-34-12 | D00837 | | 17 | | | | | SM00002 | | S | | ALL |
| 018 | 24 | | PK | 60-0 | 23-34-12 | D00837 | | 18 | | | | | SM00004 | | S | | ALL |
| 019 | 24 | | PK | 60-0 | 23-34-12 | D00837 | | 19 | | | | | SM00003 | | S | | ALL |
| 020 | 20 | | PA | 11-0 | 23-34-12 | D00837 | | 20 | | | | | GD00017 | D.. | 2 | | 050-099 |
| 020 | 20 | | PA | 10-0 | 23-34-12 | D00837 | | 20 | | | | | GD00017 | D.. | 2 | | 150-199, 275-299 |
| 025 | 24 | | PK | 16-0 | 23-34-13 | D04625J | | 25 | | | | | SM00001 | | S | | 050-099 |
| 026 | 24 | | PK | 17-0 | 23-34-13 | D00509 | | 9 | | | | | D04625J | 26 | | | ALL |
| 027 | 24 | | PK | 17-0 | 23-34-13 | D00509 | | 12 | | | | | D04625J | 27 | | | ALL |
| 028 | 22 | | PA | 10-0 | 23-34-11 | D04625J | | 45 | | | | | SM00007 | | S | | ALL |
| 032 | 20 | | PA | 6-0 | 23-34-11 | D00509 | | 2 | | | | | GD00505 | A.. | 2 | | ALL |
| 033 | 20 | | PA | 6-0 | 23-34-11 | D00509 | | 3 | | | | | GD00505 | D.. | 2 | | ALL |
| 034 | 16 | | PA | 9-0 | 23-34-11 | D00509 | | 1 | FM | | | | SP00257 | | S | | 050-099 |
| 034 | 16 | | PA | 9-0 | 23-34-11 | D00509 | | 1 | FM | | | | SP00257 | | 9 | | 150-199, 275-299 |
| 035 | 24 | | PK | 8-0 | 23-34-12 | D00509 | | 6 | | | | | SM00002 | | S | | ALL |
| 036 | 24 | | PK | 8-0 | 23-34-12 | D00509 | | 4 | | | | | SM00003 | | S | | ALL |
| 037 | 24 | | PK | 8-0 | 23-34-12 | D00509 | | 5 | | | | | SM00004 | | S | | ALL |
| 038 | 24 | | PK | 1-0 | 23-34-13 | D00509 | | 8 | | | | | SM00001 | | S | | 050-099 |
| 038 | 24 | | PK | 17-0 | 23-34-13 | D00509 | | 8 | | | | | D04625J | 52 | | | 150-199, 275-299 |
| 039 | 24 | | PK | 1-0 | 23-34-13 | D00509 | | 11 | | | | | SM00001 | | S | | 050-099 |
| 039 | 24 | | PK | 17-0 | 23-34-13 | D00509 | | 11 | | | | | D04625J | 53 | | | 150-199, 275-299 |
| 040 | 22 | | PA | 8-0 | 23-34-11 | D00509 | | 10 | | | | | SM00007 | | S | | ALL |
| 041 | 20 | | PA | 5-0 | 23-34-11 | D00523 | | 3 | | | | | GD00505 | D.. | 2 | | ALL |
| 043 | 20 | | PA | 5-0 | 23-34-11 | D00523 | | 2 | | | | | GD00505 | A.. | 2 | | ALL |
| 044 | 22 | | PA | 7-0 | 23-34-11 | D00523 | | 10 | | | | | SM00007 | | S | | ALL |
| 045 | 24 | | PK | 5-0 | 23-34-13 | D00523 | | 8 | | | | | SM00001 | | S | | 050-099 |
| 045 | 24 | | PK | 16-0 | 23-34-13 | D00523 | | 8 | | | | | D04625J | 54 | | | 150-199, 275-299 |
| 046 | 24 | | PK | 5-0 | 23-34-13 | D00523 | | 11 | | | | | SM00001 | | S | | 050-099 |
| 046 | 24 | | PK | 16-0 | 23-34-13 | D00523 | | 11 | | | | | D04625J | 55 | | | 150-199, 275-299 |
| 047 | 24 | | PK | 8-0 | 23-34-12 | D00523 | | 6 | | | | | SM00002 | | S | | ALL |
| 048 | 24 | | PK | 8-0 | 23-34-12 | D00523 | | 4 | | | | | SM00003 | | S | | ALL |
| 049 | 24 | | PK | 8-0 | 23-34-12 | D00523 | | 5 | | | | | SM00004 | | S | | ALL |
| 050 | 24 | | PK | 16-0 | 23-34-13 | D00523 | | 9 | | | | | D04625J | 24 | | | ALL |
| 051 | 24 | | PK | 16-0 | 23-34-13 | D00523 | | 12 | | | | | D04625J | 30 | | | ALL |
| 052 | 20 | | PA | 7-0 | 23-34-11 | D00533 | | 4 | | | | | GD00505 | D.. | 2 | | ALL |
| 053 | 20 | | PA | 7-0 | 23-34-11 | D00533 | | 10 | | | | | GD00505 | A.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0640

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0645 | 286T0645 | | | E2-5 TO P21 FWD LEFT ATTENDANTS PANEL (continued) | | | | | | | | | | | |
| 054 | 24 | PV | CD | 10-0 | 23-34-14 | D00533 | 14 | | | SM00005 | | 9 | | 050-099 | |
| 054 | 24 | PV | CD | 9-0 | 23-34-14 | D00533 | 14 | | | SM00005 | | 9 | | 150-199, 275-299 | |
| 054Z | | | CD | 0-0 | 23-34-14 | D00533 | 15 | | | SM00005 | REF | | FA | ALL | |
| 056 | 20 | PA | | 7-0 | 23-34-11 | D00545 | 4 | | | GD00505 | D.. | 2 | | ALL | |
| 057 | 20 | PA | | 7-0 | 23-34-11 | D00545 | 10 | | | GD00505 | A.. | 2 | | ALL | |
| 061 | 24 | PV | CK | 10-0 | 23-34-14 | D00533 | 3 | | | SM00006 | | 9 | | 050-099 | |
| 061 | 24 | PV | CK | 9-0 | 23-34-14 | D00533 | 3 | | | SM00006 | | 9 | | 150-199, 275-299 | |
| 061Z | | | CK | 0-0 | 23-34-14 | D00533 | 13 | | | SM00006 | REF | | FB | ALL | |
| 063 | 24 | PV | CM | 10-0 | 23-34-14 | D04625J | 21 | | | SM00005 | | 9 | | ALL | |
| 063Z | | | CM | 0-0 | 23-34-14 | D04625J | 22 | | | SM00005 | REF | | FA | ALL | |
| 064 | 24 | PV | CN | 10-0 | 23-34-14 | D04625J | 19 | | | SM00006 | | 9 | | ALL | |
| 064Z | | | CN | 0-0 | 23-34-14 | D04625J | 20 | | | SM00006 | REF | | FB | ALL | |
| 065 | 24 | PV | CO | 27-0 | 23-32-12 | D02519 | 54 | | | D04625J | | 41 | | 050-099, 150-199 | |
| 065B | 24 | PW | CO | 18-0 | 23-32-12 | D00533 | 8 | | | D04625J | | 42 | | 275-299 | |
| 065R | 24 | PW | CO | 0-0 | 23-32-12 | D00533 | 7 | | | D04625J | | 41 | | 275-299 | |
| 065Z | | | CO | 0-0 | 23-32-12 | D02519 | 55 | | | D04625J | | 42 | | 050-099, 150-199 | |
| 065Z | | | CO | 0-0 | 23-32-12 | D00533 | DED | | | D04625J | | | FD | 275-299 | |
| 066 | 24 | PV | CP | 27-0 | 23-32-12 | D02519 | 52 | | | D04625J | | 43 | | 050-099, 150-199 | |
| 066B | 24 | PW | CP | 18-0 | 23-32-12 | D00533 | 6 | | | D04625J | | 44 | | 275-299 | |
| 066R | 24 | PW | CP | 0-0 | 23-32-12 | D00533 | 5 | | | D04625J | | 43 | | 275-299 | |
| 066Z | | | CP | 0-0 | 23-32-12 | D02519 | 53 | | | D04625J | | 44 | | 050-099, 150-199 | |
| 066Z | | | CP | 0-0 | 23-32-12 | D00533 | DED | | | D04625J | | | FD | 275-299 | |
| 067 | 24 | PV | CQ | 27-0 | 23-32-12 | D02519 | 16 | | | D04625J | | 13 | | 050-099, 150-199 | |
| 067B | 24 | PW | CQ | 18-0 | 23-32-12 | D00545 | 8 | | | D04625J | | 14 | | 275-299 | |
| 067R | 24 | PW | CQ | 0-0 | 23-32-12 | D00545 | 7 | | | D04625J | | 13 | | 275-299 | |
| 067Z | | | CQ | 0-0 | 23-32-12 | D02519 | 17 | | | D04625J | | 14 | | 050-099, 150-199 | |
| 067Z | | | CQ | 0-0 | 23-32-12 | D00545 | DED | | | D04625J | | | FE | 275-299 | |
| 068 | 24 | PV | CR | 27-0 | 23-32-12 | D02519 | 14 | | | D04625J | | 17 | | 050-099, 150-199 | |
| 068B | 24 | PW | CR | 18-0 | 23-32-12 | D00545 | 6 | | | D04625J | | 18 | | 275-299 | |
| 068R | 24 | PW | CR | 0-0 | 23-32-12 | D00545 | 5 | | | D04625J | | 17 | | 275-299 | |
| 068Z | | | CR | 0-0 | 23-32-12 | D02519 | 15 | | | D04625J | | 18 | | 050-099, 150-199 | |
| 068Z | | | CR | 0-0 | 23-32-12 | D00545 | DED | | | D04625J | | | FE | 275-299 | |
| 069 | 20 | PA | | 12-0 | 23-34-11 | D04625J | 28 | | | GD00592 | A.. | E | | ALL | |
| 090 | 22 | PA | | 48-0 | SPARE | D04625J | 29 | | | D04493J | | 1 | | 050-099 | |
| 090 | 22 | PA | | 47-0 | SPARE | D04625J | 29 | | | D04493J | | 1 | | 150-154, 162-164 | |
| 090 | 22 | PA | | 41-0 | SPARE | D04625J | 6 | | | D06103J | | 2 | | 275-299 | |
| 091 | 24 | PV | DP | 27-0 | 23-32-12 | D05421J | 1 | | | D01879 | | 16 | | 050-099, 150-199 | |
| 091B | 24 | PW | DP | 52-0 | 23-32-12 | D05421J | 2 | | | D01869 | | 8 | | 275-299 | |
| 091R | 24 | PW | DP | 0-0 | 23-32-12 | D05421J | 1 | | | D01869 | | 7 | | 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W0640
Page 3
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0645 | 286T0645 | | | E2-5 TO P21 FWD LEFT ATTENDANTS PANEL (continued) | | | | | | | | | | | | |
| 091Z | | | | DP | 0-0 | 23-32-12 | D05421J | | 2 | | | | D01879 | 17 | | 050-099, 150-199 |
| 091Z | | | | DP | 0-0 | 23-32-12 | D05421J | | | | FF | | D01869 | DED | | 275-299 |
| 092 | 24 | PV | | DQ | 27-0 | 23-32-12 | D05421J | | 3 | | | | D01879 | 14 | | 050-099, 150-199 |
| 092B | 24 | PW | | DQ | 52-0 | 23-32-12 | D05421J | | 4 | | | | D01869 | 6 | | 275-299 |
| 092R | 24 | PW | | DQ | 0-0 | 23-32-12 | D05421J | | 3 | | | | D01869 | 5 | | 275-299 |
| 092Z | | | | DQ | 0-0 | 23-32-12 | D05421J | | 4 | | | | D01879 | 15 | | 050-099, 150-199 |
| 092Z | | | | DQ | 0-0 | 23-32-12 | D05421J | | | | FF | | D01869 | DED | | 275-299 |
| 093 | 22 | PA | | | 10-0 | 23-34-11 | D04625J | | 23 | | | | SM00013 | | S | 050-099, 150-199 |
| 093 | 22 | PA | | | 10-0 | 23-34-11 | D04625J | | 23 | | | | SM00013 | | 9 | 275-299 |
| 094 | 22 | PA | | | 10-0 | 23-34-11 | SP00261 | | | S | | | SM00013 | | S | 050-099 |
| 094 | 22 | PA | | | 10-0 | 23-34-11 | SP00261 | | 9 | | | | SM00013 | | S | 150-199 |
| 094 | 22 | PA | | | 10-0 | 23-34-11 | SP00261 | | 9 | | | | SM00013 | | 9 | 275-299 |
| 095 | 16 | PA | | | 8-0 | 23-34-11 | D00523 | | 1 | FM | | | SP00257 | | S | 050-099 |
| 095 | 16 | PA | | | 8-0 | 23-34-11 | D00523 | | 1 | FM | | | SP00257 | | 9 | 150-199, 275-299 |
| 096 | 22 | PA | | | 10-0 | 23-34-11 | D00533 | | 11 | | | | SM00013 | | S | 050-099 |
| 096 | 22 | PA | | | 8-0 | 23-34-11 | D00533 | | 11 | | | | SM00013 | | S | 150-199 |
| 096 | 22 | PA | | | 8-0 | 23-34-11 | D00533 | | 11 | | | | SM00013 | | 9 | 275-299 |
| 097 | 22 | PA | | | 6-0 | 23-34-11 | D00545 | | 11 | | | | SM00013 | | S | 050-099 |
| 097 | 22 | PA | | | 10-0 | 23-34-11 | D00545 | | 11 | | | | SM00013 | | S | 150-199 |
| 097 | 22 | PA | | | 10-0 | 23-34-11 | D00545 | | 11 | | | | SM00013 | | 9 | 275-299 |
| 098 | 22 | PA | | | 6-0 | 23-34-11 | D01869 | | 11 | | | | SM00013 | | S | 050-099 |
| 098 | 22 | PA | | | 44-0 | 23-34-11 | D01869 | | 11 | | | | SM00013 | | S | 150-199 |
| 098 | 22 | PA | | | 44-0 | 23-34-11 | D01869 | | 11 | | | | SM00013 | | 9 | 275-299 |
| 099 | 20 | PA | | | 7-0 | 23-34-11 | D01869 | | 10 | | | | GD00711 | A.. | 2 | 050-099 |
| 099 | 20 | PA | | | 9-0 | 23-34-11 | D01869 | | 10 | | | | GD00711 | A.. | 2 | 150-199, 275-299 |
| 100 | 20 | PA | | | 7-0 | 23-34-11 | D01869 | | 4 | | | | GD00711 | D.. | 2 | 050-099 |
| 100 | 20 | PA | | | 9-0 | 23-34-11 | D01869 | | 4 | | | | GD00711 | D.. | 2 | 150-199, 275-299 |
| 101 | 16 | PA | | | 39-0 | 23-34-11 | D01863 | | 1 | FM | | | SP00259 | | S | 050-099 |
| 101 | 16 | PA | | | 41-0 | 23-34-11 | D01863 | | 1 | FM | | | SP00259 | | 9 | 150-199, 275-299 |
| 102 | 22 | PA | | | 43-0 | 23-34-11 | D01863 | | 10 | | | | SM00007 | | S | ALL |
| 103 | 20 | PA | | | 6-0 | 23-34-11 | D01863 | | 2 | | | | GD00711 | A.. | 2 | 050-099 |
| 103 | 20 | PA | | | 8-0 | 23-34-11 | D01863 | | 2 | | | | GD00711 | A.. | 2 | 150-199, 275-299 |
| 104 | 20 | PA | | | 6-0 | 23-34-11 | D01863 | | 3 | | | | GD00711 | D.. | 2 | 050-099 |
| 104 | 20 | PA | | | 8-0 | 23-34-11 | D01863 | | 3 | | | | GD00711 | D.. | 2 | 150-199, 275-299 |
| 105 | 22 | PA | | | 18-0 | 23-34-11 | D01879 | | 39 | | | | SM00014 | | S | 050-099, 275-299 |
| 105 | 22 | PA | | | 19-0 | 23-34-11 | D01879 | | 39 | | | | SM00014 | | S | 150-199 |
| 106 | 20 | PA | | | 8-0 | 23-34-11 | D01879 | | 40 | | | | GD00754 | D.. | 2 | 050-099, 275-299 |
| 106 | 20 | PA | | | 9-0 | 23-34-11 | D01879 | | 40 | | | | GD00754 | D.. | 2 | 150-199 |
| 107 | 22 | PA | | | 60-0 | 23-34-11 | D00837 | | 13 | | | | SM00014 | | S | ALL |

WIRE LIST

D280T132

91-21-11

Section W0640

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0645 | 286T0645 | | | E2-5 TO P21 FWD LEFT ATTENDANTS PANEL (continued) | | | | | | | | | | | | | |
| 108 | 22 | | PA | 11-0 | 23-34-11 | D04625J | | 5 | | | | | SM00014 | | S | | ALL |
| 109 | 24 | | PK | 101-0 | 23-34-12 | D00837 | | 23 | | | | | D01863 | 15 | | | ALL |
| 110 | 24 | | PK | 44-0 | 23-34-12 | SM00002 | | | S | | | | D01863 | 6 | | | 050-099 |
| 110 | 24 | | PK | 43-0 | 23-34-12 | SM00002 | | | S | | | | D01863 | 6 | | | 150-199, 275-299 |
| 111 | 24 | | PK | 44-0 | 23-34-12 | SM00003 | | | S | | | | D01863 | 4 | | | 050-099 |
| 111 | 24 | | PK | 43-0 | 23-34-12 | SM00003 | | | S | | | | D01863 | 4 | | | 150-199, 275-299 |
| 112 | 24 | | PK | 44-0 | 23-34-12 | SM00004 | | | S | | | | D01863 | 5 | | | 050-099 |
| 112 | 24 | | PK | 43-0 | 23-34-12 | SM00004 | | | S | | | | D01863 | 5 | | | 150-199, 275-299 |
| 113 | 24 | | PK | 1-0 | 23-34-12 | D01863 | | 7 | | | | | SM00015 | | S | | ALL |
| 114 | 24 | | PK | 1-0 | 23-34-12 | SM00015 | | | S | | | | D01863 | 13 | | | ALL |
| 115 | 24 | | PK | 100-0 | 23-34-12 | D00837 | | 15 | | | | | SM00015 | | S | | ALL |
| 116 | 24 | | PK | 87-0 | 23-34-12 | D00837 | | 21 | | | | | D05421J | 10 | | | 050-099 |
| 116 | 24 | | PK | 61-0 | 23-34-12 | D00837 | | 21 | | | | | D05421J | 10 | | | 150-199, 275-299 |
| 117 | 24 | | PK | 60-0 | 23-34-12 | D00837 | | 16 | | | | | SM00016 | | S | | ALL |
| 118 | 24 | | PK | 8-0 | 23-34-12 | D00523 | | 7 | | | | | SM00016 | | S | | ALL |
| 119 | 24 | | PK | 8-0 | 23-34-12 | D00523 | | 13 | | | | | SM00016 | | S | | ALL |
| 120 | 24 | | PK | 8-0 | 23-34-12 | D00509 | | 7 | | | | | SM00016 | | S | | ALL |
| 121 | 24 | | PK | 8-0 | 23-34-12 | D00509 | | 13 | | | | | SM00016 | | S | | ALL |
| 122 | 24 | | PK | 17-0 | 23-34-12 | D05421J | | 11 | | | | | D00509 | 15 | | | ALL |
| 123 | 24 | | PK | 16-0 | 23-34-12 | D05421J | | 9 | | | | | D00523 | 15 | | | ALL |
| 124 | 24 | | PK | 45-0 | 23-34-13 | D05421J | | 5 | | | | | D01863 | 9 | | | 050-099 |
| 124 | 24 | | PK | 51-0 | 23-34-13 | D05421J | | 5 | | | | | D01863 | 9 | | | 150-199, 275-299 |
| 125 | 24 | | PK | 45-0 | 23-34-13 | D05421J | | 6 | | | | | D01863 | 12 | | | 050-099 |
| 125 | 24 | | PK | 51-0 | 23-34-13 | D05421J | | 6 | | | | | D01863 | 12 | | | 150-199, 275-299 |
| 126 | 24 | | PK | 45-0 | 23-34-13 | SM00028 | | | S | | | | D01863 | 8 | | | 050-099 |
| 126 | 24 | | PK | 51-0 | 23-34-13 | D05421J | | 7 | | | | | D01863 | 8 | | | 150-199, 275-299 |
| 127 | 24 | | PK | 41-0 | 23-34-13 | SM00028 | | | S | | | | D01863 | 11 | | | 050-099 |
| 127 | 24 | | PK | 51-0 | 23-34-13 | D05421J | | 8 | | | | | D01863 | 11 | | | 150-199, 275-299 |
| 128 | 24 | | PV | FC | 51-0 | 23-34-14 | D01879 | 29 | | | | | D06031J | 30 | | | 050-099, 150-199 |
| 128 | 24 | | PV | FC | 18-0 | 23-34-14 | D01879 | 29 | | | | | SM00006 | | 9 | | 275-299 |
| 128Z | | | | FC | 0-0 | 23-34-14 | D01879 | 30 | | | | | D06031J | 31 | | | 050-099, 150-199 |
| 128Z | | | | FC | 0-0 | 23-34-14 | D01879 | 30 | | | | | SM00006 | REF | | FB | 275-299 |
| 129 | 24 | | PV | FD | 51-0 | 23-34-14 | D01879 | 31 | | | | | D06031J | 28 | | | 050-099, 150-199 |
| 129 | 24 | | PV | FD | 18-0 | 23-34-14 | D01879 | 31 | | | | | SM00005 | | 9 | | 275-299 |
| 129Z | | | | FD | 0-0 | 23-34-14 | D01879 | 32 | | | | | D06031J | 29 | | | 050-099, 150-199 |
| 129Z | | | | FD | 0-0 | 23-34-14 | D01879 | 32 | | | | | SM00005 | REF | | FA | 275-299 |
| 130 | 24 | | PV | FE | 56-0 | 23-34-14 | D01879 | 23 | | | | | D01869 | 7 | | | 050-099, 150-199 |
| 130 | 24 | | PV | FE | 19-0 | 23-34-14 | D01879 | 23 | | | | | D00545 | 14 | | | 275-299 |
| 130Z | | | | FE | 0-0 | 23-34-14 | D01879 | 24 | | | | | D01869 | 8 | | | 050-099, 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0640
Page 5
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|-----|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0645 | 286T0645 | | | E2-5 TO P21 FWD LEFT ATTENDANTS PANEL (continued) | | | | | | | | | | | | | | |
| 130Z | | | | FE | 0-0 | 23-34-14 | D01879 | | 24 | | | | D00545 | | 15 | | | 275-299 |
| 131 | 24 | | PV | FF | 56-0 | 23-34-14 | D01879 | | 25 | | | | D01869 | | 5 | | | 050-099, 150-199 |
| 131 | 24 | | PV | FF | 19-0 | 23-34-14 | D01879 | | 25 | | | | D00545 | | 3 | | | 275-299 |
| 131Z | | | | FF | 0-0 | 23-34-14 | D01879 | | 26 | | | | D01869 | | 6 | | | 050-099, 150-199 |
| 131Z | | | | FF | 0-0 | 23-34-14 | D01879 | | 26 | | | | D00545 | | 13 | | | 275-299 |
| 132 | 24 | | PV | FG | 15-0 | 23-34-14 | D01879 | | 42 | | | | SM00025 | | | S | | 050-099, 150-199 |
| 132 | 24 | | PV | FG | 56-0 | 23-34-14 | D01879 | | 44 | | | | D01869 | | 3 | | | 275-299 |
| 132Z | | | | FG | 0-0 | 23-34-14 | D01879 | | 43 | | | | SM00025 | | | REF | FD | 050-099, 150-199 |
| 132Z | | | | FG | 0-0 | 23-34-14 | D01879 | | 45 | | | | D01869 | | 13 | | | 275-299 |
| 133 | 24 | | PV | FH | 15-0 | 23-34-14 | D01879 | | 44 | | | | SM00024 | | | S | | 050-099, 150-199 |
| 133 | 24 | | PV | FH | 56-0 | 23-34-14 | D01879 | | 42 | | | | D01869 | | 14 | | | 275-299 |
| 133Z | | | | FH | 0-0 | 23-34-14 | D01879 | | 45 | | | | SM00024 | | | REF | FC | 050-099, 150-199 |
| 133Z | | | | FH | 0-0 | 23-34-14 | D01879 | | 43 | | | | D01869 | | 15 | | | 275-299 |
| 148 | 22 | | PA | | 31-0 | 23-31-12 | D06031J | | 24 | | | | SP00399 | | | 9 | | 050-099 |
| 148 | 22 | | PA | | 39-0 | 23-31-12 | D06031J | | 24 | | | | SP00399 | | | 9 | | 150-199 |
| 148 | 22 | | PA | | 41-0 | 23-31-12 | D06103J | | 20 | | | | SP00399 | | | 9 | | 275-299 |
| 149 | 24 | | PK | | 35-0 | 23-31-12 | D06031J | | 27 | | | | D04625J | | | CAP | Y | 050-099 |
| 149 | 24 | | PK | | 37-0 | 23-31-12 | D06031J | | 27 | | | | D04625J | | 4 | | | 150-199 |
| 149 | 24 | | PK | | 41-0 | 23-31-12 | D06103J | | 1 | | | | D04625J | | 4 | | | 275-278 |
| 149 | 24 | | PV | FX | 41-0 | 23-31-12 | D06103J | | 1 | | | | D04625J | | 4 | | | 280-299 |
| 149Z | | | | FX | 0-0 | 23-31-12 | D06103J | | | DED | | | D04625J | | | DED | | 280-299 |
| 150 | 24 | | PK | | 41-0 | 23-31-12 | D06103J | | 14 | | | | D04625J | | 29 | | | 275-278 |
| 150 | 24 | | PV | GY | 41-0 | 23-31-12 | D06103J | | 14 | | | | D04625J | | 29 | | | 280-299 |
| 150Z | | | | GY | 0-0 | 23-31-12 | D06103J | | | DED | | | D04625J | | | DED | | 280-299 |
| 152 | 24 | | PK | | 41-0 | 23-31-12 | D06103J | | 24 | | | | D04625J | | 49 | | | 275-278 |
| 152 | 24 | | PV | GB | 41-0 | 23-31-12 | D06103J | | 24 | | | | D04625J | | 49 | | | 280-299 |
| 152Z | | | | GB | 0-0 | 23-31-12 | D06103J | | | DED | | | D04625J | | | DED | | 280-299 |
| 153 | 24 | | PK | | 41-0 | 23-31-12 | D06103J | | 12 | | | | D04625J | | 3 | | | 275-278 |
| 153 | 24 | | PV | GC | 41-0 | 23-31-12 | D06103J | | 12 | | | | D04625J | | 3 | | | 280-299 |
| 153Z | | | | GC | 0-0 | 23-31-12 | D06103J | | | DED | | | D04625J | | | DED | | 280-299 |
| 154 | 24 | | PK | | 41-0 | 23-31-12 | D06103J | | 3 | | | | D04625J | | 48 | | | 275-278 |
| 154 | 24 | | PV | GD | 41-0 | 23-31-12 | D06103J | | 3 | | | | D04625J | | 48 | | | 280-299 |
| 154Z | | | | GD | 0-0 | 23-31-12 | D06103J | | | DED | | | D04625J | | | DED | | 280-299 |
| 156 | 20 | | PA | | 4-0 | 23-31-12 | D06103J | | 5 | | | | GD04194 | | | D.. | 2 | 275-299 |
| 157 | 22 | | PA | | 5-0 | 23-31-12 | D06031J | | 23 | | | | GD06733 | | | S.. | 2 | 050-099 |
| 157 | 22 | | PA | | 10-0 | 23-31-12 | D06031J | | 23 | | | | GD06733 | | | S.. | 2 | 150-199 |
| 157 | 20 | | PA | | 4-0 | 23-31-12 | D06103J | | 23 | | | | GD04194 | | | S.. | 2 | 275-299 |
| 159 | 22 | | PA | | 5-0 | 23-31-12 | D06031J | | 21 | | | | GD06733 | | | A.. | 2 | 050-099 |
| 159 | 22 | | PA | | 10-0 | 23-31-12 | D06031J | | 21 | | | | GD06733 | | | A.. | 2 | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0640

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|--------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0645 | 286T0645 | | | E2-5 TO P21 FWD LEFT ATTENDANTS PANEL (continued) | | | | | | | | | | | |
| 159 | 20 | | PA | 4-0 | 23-31-12 | D06103J | | 21 | | GD04194 | A.. | 2 | | 275-299 | |
| 160 | 24 | | PK | 37-0 | 23-31-11 | D06031J | | 1 | | D05421J | | 16 | | 150-199 | |
| 161 | 24 | | PK | 37-0 | 23-31-11 | D06031J | | 2 | | D05421J | | 15 | | 150-199 | |
| 162 | 24 | | PK | 35-0 | 23-31-13 | D06031J | | 6 | | D05421J | | 18 | | 050-099 | |
| 162 | 24 | | PK | 37-0 | 23-31-13 | D06031J | | 6 | | D05421J | | 18 | | 150-199 | |
| 163 | 24 | | PK | 35-0 | 23-31-12 | D06031J | | 7 | | D04625J | | 10 | | 050-099 | |
| 163 | 24 | | PK | 37-0 | 23-31-12 | D06031J | | 7 | | D04625J | | 10 | | 150-199 | |
| 164 | 24 | | PK | 35-0 | 23-31-13 | D06031J | | 8 | | D05421J | | 20 | | 050-099 | |
| 164 | 24 | | PK | 37-0 | 23-31-13 | D06031J | | 8 | | D05421J | | 20 | | 150-199 | |
| 165 | 24 | | PK | 35-0 | 23-31-13 | D06031J | | 9 | | D05421J | | 21 | | 050-099 | |
| 165 | 24 | | PK | 37-0 | 23-31-13 | D06031J | | 9 | | D05421J | | 21 | | 150-199 | |
| 166 | 24 | | PK | 35-0 | 23-31-13 | D06031J | | 10 | | D05421J | | 22 | | 050-099 | |
| 166 | 24 | | PK | 37-0 | 23-31-13 | D06031J | | 10 | | D05421J | | 22 | | 150-199 | |
| 168 | 20 | | PA | 5-0 | 23-31-13 | D06031J | | 11 | | GD06733 | D.. | 2 | | 050, 162-166 | |
| 168 | 20 | | PA | 5-0 | 23-31-14 | D06031J | | 11 | | GD06733 | D.. | 2 | | 051-099, 150-157, 167-199 | |
| 169 | 24 | | PK | 35-0 | 23-31-13 | D06031J | | 12 | | D05421J | | 17 | | 050 | |
| 169 | 24 | | PK | 35-0 | 23-31-14 | D06031J | | 12 | | D05421J | | 17 | | 051-099 | |
| 169 | 24 | | PK | 37-0 | 23-31-14 | D06031J | | 12 | | D05421J | | 17 | | 150-157, 167-199 | |
| 169 | 24 | | PK | 37-0 | 23-31-13 | D06031J | | 12 | | D05421J | | 17 | | 162-166 | |
| 180 | 24 | | PV | HE | 15-0 | 23-34-14 | D01879 | 48 | | SM00006 | | 9 | | 050-099 | |
| 180 | 24 | | PV | HE | 19-0 | 23-34-14 | D01879 | 48 | | SM00006 | | 9 | | 150-199 | |
| 180Z | | | | HE | 0-0 | 23-34-14 | D01879 | 49 | | SM00006 | REF | | FB | 050-099, 150-199 | |
| 181 | 24 | | PV | HF | 19-0 | 23-34-14 | D01879 | 50 | | SM00005 | | 9 | | 050-099, 150-199 | |
| 181Z | | | | HF | 0-0 | 23-34-14 | D01879 | 51 | | SM00005 | REF | | FA | 050-099, 150-199 | |
| 182 | 24 | | PV | HG | 43-0 | 23-34-14 | D01869 | 3 | | SM00024 | | S | | 050-099, 150-199 | |
| 182Z | | | | HG | 0-0 | 23-34-14 | D01869 | 13 | | SM00024 | REF | | FC | 050-099, 150-199 | |
| 183 | 24 | | PV | HH | 43-0 | 23-34-14 | D01869 | 14 | | SM00025 | | S | | 050-099, 150-199 | |
| 183Z | | | | HH | 0-0 | 23-34-14 | D01869 | 15 | | SM00025 | REF | | FD | 050-099, 150-199 | |
| 184 | 24 | | PV | HI | 19-0 | 23-34-14 | D00545 | 7 | | D02519 | | 23 | | 050-099, 150-199 | |
| 184Z | | | | HI | 0-0 | 23-34-14 | D00545 | 8 | | D02519 | | 24 | | 050-099, 150-199 | |
| 185 | 24 | | PV | HJ | 19-0 | 23-34-14 | D00545 | 5 | | D02519 | | 25 | | 050-099, 150-199 | |
| 185Z | | | | HJ | 0-0 | 23-34-14 | D00545 | 6 | | D02519 | | 26 | | 050-099, 150-199 | |
| 187 | 24 | | PV | HL | 7-0 | 23-34-14 | D00545 | 14 | | SM00025 | | S | | 050-099, 150-199 | |
| 187Z | | | | HL | 0-0 | 23-34-14 | D00545 | 15 | | SM00025 | REF | | FD | 050-099, 150-199 | |
| 188 | 24 | | PV | HM | 7-0 | 23-34-14 | D00545 | 3 | | SM00024 | | S | | 050-099, 150-199 | |
| 188Z | | | | HM | 0-0 | 23-34-14 | D00545 | 13 | | SM00024 | REF | | FC | 050-099, 150-199 | |
| 189 | 24 | | PV | HN | 19-0 | 23-34-14 | D02519 | 42 | | D00533 | | 7 | | 050-099, 150-199 | |
| 189Z | | | | HN | 0-0 | 23-34-14 | D02519 | 43 | | D00533 | | 8 | | 050-099, 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0640

Page 7

Mar 14/2007



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0645 | 286T0645 | | | E2-5 TO P21 FWD LEFT ATTENDANTS PANEL (continued) | | | | | | | | | | | | | |
| 190 | 24 | PV | HO | | 19-0 | 23-34-14 | D02519 | | 44 | | | D00533 | | 5 | | 050-099, 150-199 | |
| 190Z | | | HO | | 0-0 | 23-34-14 | D02519 | | 45 | | | D00533 | | 6 | | 050-099, 150-199 | |
| 191 | 24 | PV | HP | | 3-0 | 23-34-14 | D01879 | | 33 | | | D02519 | | 31 | | 050-099 | |
| 191 | 24 | PV | HP | | 4-0 | 23-34-14 | D01879 | | 33 | | | D02519 | | 31 | | 150-199 | |
| 191Z | | | HP | | 0-0 | 23-34-14 | D01879 | | 34 | | | D02519 | | 32 | | 050-099, 150-199 | |
| 192 | 24 | PV | HQ | | 3-0 | 23-34-14 | D01879 | | 35 | | | D02519 | | 29 | | 050-099 | |
| 192 | 24 | PV | HQ | | 4-0 | 23-34-14 | D01879 | | 35 | | | D02519 | | 29 | | 150-199 | |
| 192Z | | | HQ | | 0-0 | 23-34-14 | D01879 | | 36 | | | D02519 | | 30 | | 050-099, 150-199 | |
| 193 | 22 | PA | | | 19-0 | 23-34-11 | D02519 | | 39 | | | SM00014 | | | S | 050-099, 150-199 | |
| 194 | 20 | PA | | | 8-0 | 23-34-11 | D02519 | | 40 | | | GD00754 | | D.. | 2 | 050-099, 150-199 | |
| 201B | 24 | PL | IA | | 18-0 | 23-31-13 | D00533 | | 2 | | | D04625J | | 47 | | 050-099, 150-199 | |
| 201B | 24 | PL | IA | | 9-0 | 23-31-13 | D00533 | | 2 | | | SM00009 | | | S | 275-299 | |
| 201R | 24 | PL | IA | | 0-0 | 23-31-13 | D00533 | | 1 | | | D04625J | | 46 | | 050-099, 150-199 | |
| 201R | 24 | PL | IA | | 0-0 | 23-31-13 | D00533 | | 1 | | | SM00008 | | | S | 275-299 | |
| 202B | 24 | PL | IB | | 18-0 | 23-31-13 | D00545 | | 2 | | | D04625J | | 49 | | 050-099, 150-199 | |
| 202B | 24 | PL | IB | | 10-0 | 23-31-13 | D00545 | | 2 | | | SM00009 | | | S | 275-299 | |
| 202R | 24 | PL | IB | | 0-0 | 23-31-13 | D00545 | | 1 | | | D04625J | | 48 | | 050-099, 150-199 | |
| 202R | 24 | PL | IB | | 0-0 | 23-31-13 | D00545 | | 1 | | | SM00008 | | | S | 275-299 | |
| 203B | 24 | PL | IC | | 10-0 | 23-31-13 | D04625J | | 16 | | | SM00009 | | | S | 275-299 | |
| 203R | 24 | PL | IC | | 0-0 | 23-31-13 | D04625J | | 15 | | | SM00008 | | | S | 275-299 | |
| 209B | 24 | PL | II | | 1-0 | 23-34-14 | D01879 | | 49 | | | D01879 | | 36 | | 275-299 | |
| 209R | 24 | PL | II | | 0-0 | 23-34-14 | D01879 | | 35 | | | D01879 | | 48 | | 275-299 | |
| 210B | 24 | PL | IJ | | 1-0 | 23-34-14 | D01879 | | 51 | | | D01879 | | 34 | | 275-299 | |
| 210R | 24 | PL | IJ | | 0-0 | 23-34-14 | D01879 | | 50 | | | D01879 | | 33 | | 275-299 | |
| 211B | 24 | PL | IK | | 52-0 | 23-31-13 | D01869 | | 2 | | | D04625J | | 51 | | 050-099, 150-199 | |
| 211B | 24 | PL | IK | | 44-0 | 23-31-13 | D01869 | | 2 | | | SM00009 | | | S | 275-299 | |
| 211R | 24 | PL | IK | | 0-0 | 23-31-13 | D01869 | | 1 | | | D04625J | | 50 | | 050-099, 150-199 | |
| 211R | 24 | PL | IK | | 0-0 | 23-31-13 | D01869 | | 1 | | | SM00008 | | | S | 275-299 | |
| 212 | 20 | UA | | | 1-6 | 23-22-12 | GD00434 | | S.. | 2 | | D06069J | | | | IL | 275-278 |
| 212B | 24 | PW | IL | | 35-0 | 23-22-12 | D05421J | | 25 | | | D06031J | | 14 | | 050-099 | |
| 212B | 24 | PW | IL | | 37-0 | 23-22-12 | D05421J | | 25 | | | D06031J | | 14 | | 150-199 | |
| 212B | 24 | PW | IL | | 48-0 | 23-22-12 | D05421J | | 25 | | | D06069J | | 14 | | 275-278 | |
| 212R | 24 | PW | IL | | 0-0 | 23-22-12 | D05421J | | 24 | | | D06031J | | 13 | | 050-099, 150-199 | |
| 212R | 24 | PW | IL | | 0-0 | 23-22-12 | D05421J | | 24 | | | D06069J | | 13 | | 275-278 | |
| 212Z | | | IL | | 0-0 | 23-22-12 | D05421J | | 26 | | | D06031J | | 15 | | 050-099, 150-199 | |
| 212Z | | | IL | | 0-0 | 23-22-12 | D05421J | | 26 | | | D06069J | | | | IL | 275-278 |
| 213 | 20 | UA | | | 1-6 | 23-22-12 | GD00434 | | S.. | 2 | | D06069J | | | | IM | 275-278 |
| 213B | 24 | PW | IM | | 35-0 | 23-22-12 | D05421J | | 28 | | | D06031J | | 17 | | 050-099 | |
| 213B | 24 | PW | IM | | 37-0 | 23-22-12 | D05421J | | 28 | | | D06031J | | 17 | | 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0640

Page 8

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0645 | 286T0645 | | | E2-5 TO P21 FWD LEFT ATTENDANTS PANEL (continued) | | | | | | | | | | | |
| 213B | 24 | | PW | IM | 48-0 | 23-22-12 | D05421J | 28 | | | D06069J | 17 | | | 275-278 |
| 213R | 24 | | PW | IM | 0-0 | 23-22-12 | D05421J | 27 | | | D06031J | 16 | | | 050-099, 150-199 |
| 213R | 24 | | PW | IM | 0-0 | 23-22-12 | D05421J | 27 | | | D06069J | 16 | | | 275-278 |
| 213Z | | | | IM | 0-0 | 23-22-12 | D05421J | 29 | | | D06031J | 18 | | | 050-099, 150-199 |
| 213Z | | | | IM | 0-0 | 23-22-12 | D05421J | 29 | | | D06069J | | | IM | 275-278 |
| 214B | 20 | | PB | IN | 35-0 | 23-22-12 | D05421J | 31 | | | D06031J | 20 | | | 050-099 |
| 214B | 20 | | PB | IN | 37-0 | 23-22-12 | D05421J | 31 | | | D06031J | 20 | | | 150-199 |
| 214B | 20 | | PB | IN | 48-0 | 23-22-12 | D05421J | 31 | | | D06069J | 20 | | | 275-278 |
| 214R | 20 | | PB | IN | 0-0 | 23-22-12 | D05421J | 30 | | | D06031J | 19 | | | 050-099, 150-199 |
| 214R | 20 | | PB | IN | 0-0 | 23-22-12 | D05421J | 30 | | | D06069J | 19 | | | 275-278 |
| 215B | 24 | | PW | IO | 35-0 | 23-31-12 | D06031J | 25 | | | D04625J | 8 | | | 050-099 |
| 215B | 24 | | PW | IO | 39-0 | 23-31-12 | D06031J | 25 | | | D04625J | 8 | | | 150-199 |
| 215B | 24 | | PW | IO | 43-0 | 23-31-12 | D06103J | 18 | | | D04625J | 50 | | | 275-299 |
| 215R | 24 | | PW | IO | 0-0 | 23-31-12 | D06031J | 26 | | | D04625J | 9 | | | 050-099, 150-199 |
| 215R | 24 | | PW | IO | 0-0 | 23-31-12 | D06103J | 7 | | | D04625J | 2 | | | 275-299 |
| 215Z | | | | IO | 0-0 | 23-31-12 | D06031J | 22 | | | D04625J | 7 | | | 050-099, 150-199 |
| 215Z | | | | IO | 0-0 | 23-31-12 | D06103J | 22 | | | D04625J | 7 | | | 275-299 |
| 216B | 24 | | PW | IP | 41-0 | 23-31-12 | D06103J | 17 | | | D04625J | 46 | | | 275-299 |
| 216R | 24 | | PW | IP | 0-0 | 23-31-12 | D06103J | 6 | | | D04625J | 47 | | | 275-299 |
| 216Z | | | | IP | 0-0 | 23-31-12 | D06103J | 19 | | | D04625J | 8 | | | 275-299 |
| 217B | 24 | | PW | IQ | 37-0 | 23-31-11 | D06031J | 4 | | | D05421J | 12 | | | 150-199 |
| 217R | 24 | | PW | IQ | 0-0 | 23-31-11 | D06031J | 3 | | | D05421J | 13 | | | 150-199 |
| 217Z | | | | IQ | 0-0 | 23-31-11 | D06031J | 5 | | | D05421J | 14 | | | 150-199 |
| 224B | 24 | | PL | IX | 1-0 | 23-34-14 | D02519 | 49 | | | D02519 | 36 | | | 050-099, 150-199 |
| 224R | 24 | | PL | IX | 0-0 | 23-34-14 | D02519 | 35 | | | D02519 | 48 | | | 050-099, 150-199 |
| 225B | 24 | | PL | IY | 1-0 | 23-34-14 | D02519 | 51 | | | D02519 | 34 | | | 050-099, 150-199 |
| 225R | 24 | | PL | IY | 0-0 | 23-34-14 | D02519 | 50 | | | D02519 | 33 | | | 050-099, 150-199 |
| 301B | 24 | | PM | A | 35-0 | 23-31-12 | D00837 | 3 | | | D04625J | 3 | | | 050-099 |
| 301R | 24 | | PM | A | 0-0 | 23-31-12 | D00837 | 1 | | | D04625J | 1 | | | 050-099 |
| 301Y | 24 | | PM | A | 0-0 | 23-31-12 | D00837 | 2 | | | D04625J | 2 | | | 050-099 |
| 401B | 24 | | PY | QA | 44-0 | 23-42-11 | D04625J | 37 | | | D00857 | 3 | | | 050-099, 150-199 |
| 401B | 24 | | PY | A | 43-0 | 23-42-11 | D04625J | 37 | | | D00857 | 3 | | | 275-299 |
| 401G | 24 | | PY | QA | 0-0 | 23-42-11 | D04625J | 39 | | | D00857 | 5 | | | 050-099, 150-199 |
| 401G | 24 | | PY | A | 0-0 | 23-42-11 | D04625J | 39 | | | D00857 | 5 | | | 275-299 |
| 401R | 24 | | PY | QA | 0-0 | 23-42-11 | D04625J | 36 | | | D00857 | 1 | | | 050-099, 150-199 |
| 401R | 24 | | PY | A | 0-0 | 23-42-11 | D04625J | 36 | | | D00857 | 1 | | | 275-299 |
| 401Y | 24 | | PY | QA | 0-0 | 23-42-11 | D04625J | 38 | | | D00857 | 4 | | | 050-099, 150-199 |
| 401Y | 24 | | PY | A | 0-0 | 23-42-11 | D04625J | 38 | | | D00857 | 4 | | | 275-299 |
| 401Z | | | | QA | 0-0 | 23-42-11 | D04625J | 40 | | | D00857 | 2 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11
Section W0640
Page 9
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0645 | 286T0645 | | | E2-5 TO P21 FWD LEFT ATTENDANTS PANEL (continued) | | | | | | | | | | | |
| 401Z | | | | A | 0-0 | 23-42-11 | D04625J | 40 | | | | D00857 | 2 | | 275-299 |
| 402B | 24 | PY | | QB | 40-0 | 23-42-11 | D04625J | 32 | | | | SM00019 | 9 | | 050-099, 150-199 |
| 402B | 24 | PY | | B | 62-0 | 23-42-11 | D04625J | 32 | | | | D00859 | 3 | \$D | 275-299 |
| 402G | 24 | PY | | QB | 0-0 | 23-42-11 | D04625J | 34 | | | | SM00021 | 9 | | 050-099, 150-199 |
| 402G | 24 | PY | | B | 0-0 | 23-42-11 | D04625J | 34 | | | | D00859 | 5 | \$D | 275-299 |
| 402R | 24 | PY | | QB | 0-0 | 23-42-11 | D04625J | 31 | | | | SM00018 | 9 | | 050-099, 150-199 |
| 402R | 24 | PY | | B | 0-0 | 23-42-11 | D04625J | 31 | | | | D00859 | 1 | \$D | 275-299 |
| 402Y | 24 | PY | | QB | 0-0 | 23-42-11 | D04625J | 33 | | | | SM00020 | 9 | | 050-099, 150-199 |
| 402Y | 24 | PY | | B | 0-0 | 23-42-11 | D04625J | 33 | | | | D00859 | 4 | \$D | 275-299 |
| 402Z | | | | QB | 0-0 | 23-42-11 | D04625J | 35 | | | | SM00022 | 9 | | 050-099 |
| 402Z | | | | QB | 0-0 | 23-42-11 | D04625J | 35 | | | | SM00022 | S | | 150-199 |
| 402Z | | | | B | 0-0 | 23-42-11 | D04625J | 35 | | | | D00859 | 2 | \$D | 275-299 |
| 405B | 24 | PY | | QE | 23-0 | 23-42-11 | SM00019 | | 9 | | | D00859 | 3 | | 050-099, 150-199 |
| 405G | 24 | PY | | QE | 0-0 | 23-42-11 | SM00021 | | 9 | | | D00859 | 5 | | 050-099, 150-199 |
| 405R | 24 | PY | | QE | 0-0 | 23-42-11 | SM00018 | | 9 | | | D00859 | 1 | | 050-099, 150-199 |
| 405Y | 24 | PY | | QE | 0-0 | 23-42-11 | SM00020 | | 9 | | | D00859 | 4 | | 050-099, 150-199 |
| 405Z | | | | QE | 0-0 | 23-42-11 | SM00022 | | 9 | | | D00859 | 2 | | 050-099 |
| 405Z | | | | QE | 0-0 | 23-42-11 | SM00022 | | S | | | D00859 | 2 | | 150-199 |
| 406B | 24 | PY | | QF | 11-0 | 23-42-11 | SM00019 | | 9 | | | D06730 | 3 | | 050-099, 150-199 |
| 406G | 24 | PY | | QF | 0-0 | 23-42-11 | SM00021 | | 9 | | | D06730 | 5 | | 050-099, 150-199 |
| 406R | 24 | PY | | QF | 0-0 | 23-42-11 | SM00018 | | 9 | | | D06730 | 1 | | 050-099, 150-199 |
| 406Y | 24 | PY | | QF | 0-0 | 23-42-11 | SM00020 | | 9 | | | D06730 | 4 | | 050-099, 150-199 |
| 406Z | | | | QF | 0-0 | 23-42-11 | SM00022 | | 9 | | | D06730 | 2 | | 050-099 |
| 406Z | | | | QF | 0-0 | 23-42-11 | SM00022 | | S | | | D06730 | 2 | | 150-199 |
| 407B | 24 | PY | | QG | 10-0 | 23-42-11 | D06031J | 37 | | | | SM00019 | 9 | | 050-099 |
| 407B | 24 | PY | | QG | 11-0 | 23-42-11 | SM00019 | | 9 | | | D06031J | 37 | | 162-199 |
| 407G | 24 | PY | | QG | 0-0 | 23-42-11 | D06031J | 39 | | | | SM00021 | 9 | | 050-099 |
| 407G | 24 | PY | | QG | 0-0 | 23-42-11 | SM00021 | | 9 | | | D06031J | 39 | | 162-199 |
| 407R | 24 | PY | | QG | 0-0 | 23-42-11 | D06031J | 36 | | | | SM00018 | 9 | | 050-099 |
| 407R | 24 | PY | | QG | 0-0 | 23-42-11 | SM00018 | | 9 | | | D06031J | 36 | | 162-199 |
| 407Y | 24 | PY | | QG | 0-0 | 23-42-11 | D06031J | 38 | | | | SM00020 | 9 | | 050-099 |
| 407Y | 24 | PY | | QG | 0-0 | 23-42-11 | SM00020 | | 9 | | | D06031J | 38 | | 162-199 |
| 407Z | | | | QG | 0-0 | 23-42-11 | D06031J | 40 | | | | SM00022 | 9 | | 050-099 |
| 407Z | | | | QG | 0-0 | 23-42-11 | SM00022 | | S | | | D06031J | 40 | | 162-199 |
| 507 | 24 | PK | | | 62-0 | 23-34-13 | D00837 | 10 | | | | D04625J | 51 | | 275-278 |
| 507 | 24 | PK | | | 61-1 | 23-34-13 | D00837 | 10 | | | | D04625J | 51 | | 280-299 |
| 508 | 24 | PK | | | 35-0 | 23-42-11 | D04625J | 52 | | | | D06031J | 32 | | 050-099 |
| 508 | 24 | PK | | | 36-0 | 23-42-11 | D04625J | 25 | | | | D06031J | 32 | | 162-199 |
| 509 | 22 | PA | | | 35-0 | 23-42-11 | D04625J | 6 | | | | D06031J | 41 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0640

Page 10

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0645 | 286T0645 | | | E2-5 TO P21 FWD LEFT ATTENDANTS PANEL (continued) | | | | | | | | | | | | |
| 509 | 22 | | PA | | 36-0 | 23-42-11 | D04625J | 6 | | | D06031J | 41 | | | 162-199 | |
| 512 | 24 | | PK | | 5-0 | 23-34-13 | SM00028 | | S | | SM00001 | | S | | 050-099 | |
| 614 | 22 | | PA | | 27-0 | 23-32-12 | D04625J | 15 | | | D02519 | 20 | | | 050-099, 150-199 | |
| 615 | 22 | | PA | | 27-0 | 23-32-12 | D04625J | 16 | | | D02519 | 21 | | | 050-099, 150-199 | |
| 616 | 22 | | PA | | 27-0 | 23-32-12 | D05421J | 19 | | | D01879 | 21 | | | 050-099, 150-199 | |
| 901 | 24 | | PK | | 35-0 | 23-31-11 | D00837 | 6 | | | D05421J | 15 | | | 050-099 | |
| 902 | 24 | | PK | | 35-0 | 23-31-11 | D00837 | 7 | | | D05421J | 16 | | | 050-099 | |
| 903B | 24 | | PW | IQ | 35-0 | 23-31-11 | D00837 | 9 | | | D05421J | 13 | | | 050-099 | |
| 903R | 24 | | PW | IQ | 0-0 | 23-31-11 | D00837 | 8 | | | D05421J | 12 | | | 050-099 | |
| 903Z | | | | IQ | 0-0 | 23-31-11 | D00837 | 10 | | | D05421J | 14 | | | 050-099 | |
| FRA | | | | | 0-0 | 23-22-12 | D06069J | | | IL | D06069J | 15 | | | 275-278 | |
| FRB | | | | | 0-0 | 23-22-12 | D06069J | | | IM | D06069J | 18 | | | 275-278 | |
| FRD | | | | | 0-0 | 23-32-12 | D04625J | 9 | | | D04625J | | | FD | 275-299 | |
| FRE | | | | | 0-0 | 23-32-12 | D04625J | 10 | | | D04625J | | | FE | 275-299 | |
| FRF | | | | | 0-0 | 23-32-12 | D05421J | | | FF | D05421J | 12 | | | 275-299 | |
| W0646 | 286T0646 | | | CARGO COMPARTMENT FIRE EXTINGUISHING BOTTLE 1 | | | | | | | | | | | | |
| 001R | 20 | | PH | | 2-0 | 26-23-11 | D01448 | 2 | | | D06894J | 5 | | | 155-199, 275-299 | |
| 002R | 20 | | PH | | 3-0 | 26-23-11 | D01440 | 1 | | | D06894J | 8 | | | 155-199, 275-299 | |
| 003R | 20 | | PH | | 2-0 | 26-23-11 | D01442 | 1 | | | D06894J | 11 | | | 155-199, 275-299 | |
| 004R | 20 | | PH | | 2-0 | 26-23-11 | D01448 | 3 | | | GD05810 | D.. | E | * | 155-199, 275-299 | |
| 005R | 20 | | PH | | 3-0 | 26-23-11 | D01440 | 2 | | | GD05810 | D.. | E | * | 155-199, 275-299 | |
| 006R | 20 | | PH | | 2-0 | 26-23-11 | D01442 | 2 | | | GD05810 | D.. | E | * | 155-199, 275-299 | |
| 007R | 20 | | PH | | 2-0 | 26-23-11 | D01448 | 1 | | | GD05812 | S.. | E | * | 155-199, 275-299 | |
| 008R | 20 | | PH | | 3-0 | 26-23-11 | D01440 | 3 | | | GD05812 | S.. | E | * | 155-199, 275-299 | |
| 009R | 20 | | PH | | 2-0 | 26-23-11 | D01442 | 3 | | | GD05812 | S.. | E | * | 155-199, 275-299 | |
| W0647 | 286T0647 | | | E2-5 TO AFT ATTENDANTS HANDSETS | | | | | | | | | | | | |
| 008 | 22 | | PA | | 133-0 | 23-24-11 | D04629J | 12 | | | M01597 | ON | C | | 050-099 | |
| 008 | 22 | | PA | | 154-0 | 23-24-11 | D04629J | 12 | | | M01597 | ON | C | | 150-199 | |
| 009 | 22 | | PA | | 133-0 | 23-24-11 | D04629J | 13 | | | M01597 | ARM | C | | 050-099 | |
| 009 | 22 | | PA | | 154-0 | 23-24-11 | D04629J | 13 | | | M01597 | ARM | C | | 150-199 | |
| 401B | 24 | | PY | A | 150-0 | 23-42-11 | D04629J | 2 | | | D00853 | 3 | \$D | | 050-099 | |
| 401B | 24 | | PY | A | 173-0 | 23-42-11 | D04629J | 2 | | | D00853 | 3 | \$D | | 150-199 | |
| 401B | 24 | | PY | A | 171-0 | 23-42-11 | D04629J | 2 | | | D00853 | 3 | \$D | | 275-299 | |
| 401G | 24 | | PY | A | 0-0 | 23-42-11 | D04629J | 4 | | | D00853 | 5 | \$D | | ALL | |
| 401R | 24 | | PY | A | 0-0 | 23-42-11 | D04629J | 1 | | | D00853 | 1 | \$D | | ALL | |
| 401Y | 24 | | PY | A | 0-0 | 23-42-11 | D04629J | 3 | | | D00853 | 4 | \$D | | ALL | |
| 401Z | | | | A | 0-0 | 23-42-11 | D04629J | 5 | | | D00853 | 2 | \$D | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0640

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0647 | 286T0647 | | | E2-5 TO AFT ATTENDANTS HANDSETS (continued) | | | | | | | | | | | | |
| 402B | 24 | PY | B | 150-0 | 23-42-11 | D04629J | | 8 | | | | D00855 | 3 | \$D | | 050-099 |
| 402B | 24 | PY | B | 173-0 | 23-42-11 | D04629J | | 8 | | | | D00855 | 3 | \$D | | 150-199 |
| 402B | 24 | PY | B | 172-0 | 23-42-11 | D04629J | | 8 | | | | D00855 | 3 | \$D | | 275-299 |
| 402G | 24 | PY | B | 0-0 | 23-42-11 | D04629J | | 10 | | | | D00855 | 5 | \$D | | ALL |
| 402R | 24 | PY | B | 0-0 | 23-42-11 | D04629J | | 7 | | | | D00855 | 1 | \$D | | ALL |
| 402Y | 24 | PY | B | 0-0 | 23-42-11 | D04629J | | 9 | | | | D00855 | 4 | \$D | | ALL |
| 402Z | | | B | 0-0 | 23-42-11 | D04629J | | 11 | | | | D00855 | 2 | \$D | | ALL |
| W0648 | 286T0648 | | | CARGO COMPARTMENT FIRE EXTINGUISHING BOTTLE 2 | | | | | | | | | | | | |
| 001R | 20 | PH | | 2-0 | 26-23-12 | D01454 | | 2 | | | | D06896J | 6 | | | 155-199, 275-299 |
| 002R | 20 | PH | | 3-0 | 26-23-12 | D01450 | | 1 | | | | D06896J | 9 | | | 155-199, 275-299 |
| 003R | 20 | PH | | 2-0 | 26-23-12 | D01452 | | 1 | | | | D06896J | 12 | | | 155-199, 275-299 |
| 004R | 20 | PH | | 2-0 | 26-23-12 | D01454 | | 3 | | | | GD05826 | D.. | E | * | 155-199, 275-299 |
| 005R | 20 | PH | | 3-0 | 26-23-12 | D01450 | | 2 | | | | GD05826 | D.. | E | * | 155-199, 275-299 |
| 006R | 20 | PH | | 2-0 | 26-23-12 | D01452 | | 2 | | | | GD05826 | D.. | E | * | 155-199, 275-299 |
| 007R | 20 | PH | | 2-0 | 26-23-12 | D01454 | | 1 | | | | GD05828 | S.. | E | * | 155-199, 275-299 |
| 008R | 20 | PH | | 3-0 | 26-23-12 | D01450 | | 3 | | | | GD05828 | S.. | E | * | 155-199, 275-299 |
| 009R | 20 | PH | | 2-0 | 26-23-12 | D01452 | | 3 | | | | GD05828 | S.. | E | * | 155-199, 275-299 |
| W0649 | 286T0649 | | | E2-5 SHELF TO VOICE RECORDER | | | | | | | | | | | | |
| 001 | 20 | PA | | 144-0 | 23-71-11 | D04633J | | 1 | | | | GD00175 | S.. | E | * | 050-099 |
| 001 | 20 | PA | | 163-0 | 23-71-11 | D04633J | | 1 | | | | GD00175 | S.. | E | * | 150-199, 275-299 |
| 002 | 22 | PA | | 143-0 | 23-71-11 | D04633J | | 2 | | | | D00273 | 2 | | | 050-099 |
| 002 | 22 | PA | | 162-0 | 23-71-11 | D04633J | | 2 | | | | D00273 | 2 | | | 150-199, 275-299 |
| 003 | 20 | PA | | 7-0 | 23-71-11 | GD00173 | | A.. | E | | | D00273 | 3 | | | 050-099 |
| 003 | 20 | PA | | 5-0 | 23-71-11 | GD00173 | | A.. | E | | | D00273 | 3 | | | 150-199, 275-299 |
| 006 | 24 | PV | AF | 143-0 | 23-71-11 | D04633J | | 6 | | | | D00273 | 6 | | | 050-099 |
| 006 | 24 | PV | AF | 162-0 | 23-71-11 | D04633J | | 6 | | | | D00273 | 6 | | | 150-199, 275-299 |
| 006Z | | | AF | 0-0 | 23-71-11 | D04633J | | 5 | | | | D00273 | 5 | | | ALL |
| 007 | 24 | PK | | 1-0 | 23-71-11 | D00273 | | 7 | | | | D00273 | 8 | | | ALL |
| 008 | 24 | PK | | 143-0 | 23-71-11 | D04633J | | 8 | | | | D00273 | 57 | | | 050-099 |
| 008 | 24 | PK | | 162-0 | 23-71-11 | D04633J | | 8 | | | | D00273 | 57 | | | 150-199, 275-299 |
| 009 | 24 | PK | | 143-0 | 23-71-11 | D04633J | | 9 | | | | D00273 | 55 | | | 050-099 |
| 009 | 24 | PK | | 162-0 | 23-71-11 | D04633J | | 9 | | | | D00273 | 55 | | | 150-199, 275-299 |
| 010 | 24 | PV | AJ | 143-0 | 23-71-11 | D04633J | | 10 | | | | D00273 | 47 | | | 050-099 |
| 010 | 24 | PV | AJ | 162-0 | 23-71-11 | D04633J | | 10 | | | | D00273 | 47 | | | 150-199, 275-299 |
| 010Z | | | AJ | 0-0 | 23-71-11 | D04633J | | 11 | | | | D00273 | 45 | | | ALL |
| 012 | 24 | PK | | 143-0 | 23-71-11 | D04633J | | 12 | | | | D00273 | 12 | | | 050-099 |
| 012 | 24 | PK | | 162-0 | 23-71-11 | D04633J | | 12 | | | | D00273 | 12 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0640

Page 12

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0649 | 286T0649 | | | E2-5 SHELF TO VOICE RECORDER (continued) | | | | | | | | | | | |
| 013 | 24 | | PK | | 143-0 | 23-71-11 | D04633J | | | | | | | | 050-099 |
| 013 | 24 | | PK | | 162-0 | 23-71-11 | D04633J | | | | | | | | 150-199, 275-299 |
| 014 | 22 | | PA | | 143-0 | 23-71-11 | D04633J | | | | | | | | 050-099 |
| 014 | 22 | | PA | | 162-0 | 23-71-11 | D04633J | | | | | | | | 150-199, 275-299 |
| 015 | 24 | | PK | | 143-0 | 23-71-11 | D04633J | | | | | | | | 050-099 |
| 015 | 24 | | PK | | 162-0 | 23-71-11 | D04633J | | | | | | | | 150-199, 275-299 |
| 016 | 24 | | PK | | 143-0 | 23-71-11 | D04633J | | | | | | | | 050-099 |
| 016 | 24 | | PK | | 162-0 | 23-71-11 | D04633J | | | | | | | | 150-199, 275-299 |
| 017 | 20 | | PA | | 4-0 | 23-71-11 | GD00175 | S.. | E | * | | | | | ALL |
| 018 | 24 | | PV | AR | 141-0 | 23-51-41 | D04633J | | | | | | | | 050-099 |
| 018 | 24 | | PV | AR | 162-0 | 23-51-41 | D04633J | | | | | | | | 150-199, 275-299 |
| 018Z | | | | AR | 0-0 | 23-51-41 | D04633J | | | | | | | | ALL |
| 020 | 24 | | PV | AT | 143-0 | 23-51-21 | D04633J | | | | | | | | 050-099 |
| 020 | 24 | | PV | AT | 162-0 | 23-51-21 | D04633J | | | | | | | | 150-199, 275-299 |
| 020Z | | | | AT | 0-0 | 23-51-21 | D04633J | | | | | | | | ALL |
| 023 | 24 | | PK | | 143-0 | 23-71-11 | D04633J | | | | | | | | 050-099 |
| 023 | 24 | | PK | | 162-0 | 23-71-11 | D04633J | | | | | | | | 150-199, 275-299 |
| 024 | 24 | | PK | | 143-0 | 23-71-11 | D04633J | | | | | | | | 050-099 |
| 024 | 24 | | PK | | 162-0 | 23-71-11 | D04633J | | | | | | | | 150-199, 275-299 |
| 025 | 24 | | PK | | 143-0 | 23-71-11 | D04633J | | | | | | | | 050-099 |
| 025 | 24 | | PK | | 162-0 | 23-71-11 | D04633J | | | | | | | | 150-199, 275-299 |
| 026 | 24 | | PV | BA | 143-0 | 23-51-13 | D04633J | | | | | | | | 050-099 |
| 026 | 24 | | PV | BA | 162-0 | 23-51-13 | D04633J | | | | | | | | 150-199, 275-299 |
| 026Z | | | | BA | 0-0 | 23-51-13 | D04633J | | | | | | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0640
Page 13 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|--|-----------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0650 | 286T0650 | | | CARGO COMPARTMENT FIRE EXTINGUISHING BOTTLE 2A | | | | | | | | | | | | | | |
| 001R | 20 | | PH | 4-0 | 26-23-12 | D10684 | | | 2 | | | | D06898J | | 8 | | | 155-199, 275-299 |
| 002R | 20 | | PH | 2-0 | 26-23-12 | D10680 | | | 1 | | | | D06898J | | 12 | | | 155-199, 275-299 |
| 003R | 20 | | PH | 2-0 | 26-23-12 | D10682 | | | 1 | | | | D06898J | | 15 | | | 155-199, 275-299 |
| 004R | 20 | | PH | 4-0 | 26-23-12 | D10684 | | | 3 | | | | GD05854 | D.. | E | * | | 155-199, 275-299 |
| 005R | 20 | | PH | 2-0 | 26-23-12 | D10680 | | | 2 | | | | GD05854 | D.. | E | * | | 155-199, 275-299 |
| 006R | 20 | | PH | 3-0 | 26-23-12 | D10682 | | | 2 | | | | GD05854 | D.. | E | * | | 155-199, 275-299 |
| 007R | 20 | | PH | 4-0 | 26-23-12 | D10684 | | | 1 | | | | GD05856 | S.. | E | * | | 155-199, 275-299 |
| 008R | 20 | | PH | 2-0 | 26-23-12 | D10680 | | | 3 | | | | GD05856 | S.. | E | * | | 155-199, 275-299 |
| 009R | 20 | | PH | 3-0 | 26-23-12 | D10682 | | | 3 | | | | GD05856 | S.. | E | * | | 155-199, 275-299 |
| W0654 | 286T0654 | | | AIR COND FEEDER | | | | | | | | | | | | | | |
| 001 | 24 | | PK | 22-0 | 24-51-71 | D04960J | | | 1 | | | | D05060P | | 1 | | | ALL |
| 002 | 24 | | PK | 22-0 | 24-51-71 | D04960J | | | 2 | | | | D05060P | | 2 | | | ALL |
| 003 | 24 | | PK | 22-0 | 24-51-71 | D04960J | | | 3 | | | | D05060P | | 3 | | | ALL |
| 004 | 24 | | PK | 22-0 | 24-51-71 | D04960J | | | 4 | | | | D05060P | | 4 | | | ALL |
| 028 | 24 | | PK | 33-0 | 21-31-11 | D05186P | | | 31 | | | | D04912J | | 6 | | | ALL |
| 029 | 24 | | PK | 33-0 | 21-31-11 | D05186P | | | 29 | | | | D04912J | | 7 | | | ALL |
| 030 | 24 | | PK | 33-0 | 21-31-11 | D05186P | | | 30 | | | | D04912J | | 8 | | | ALL |
| 033 | 20 | | PA | 33-0 | 21-31-11 | D05186P | | | 19 | | | | D04912J | | 19 | | | ALL |
| 034 | 24 | | PK | 50-0 | 21-44-21 | D05060P | | | 7 | | | | D04698J | | 10 | | | 050-099 |
| 034 | 24 | | PK | 60-0 | 21-44-21 | D05060P | | | 7 | | | | D04698J | | 10 | | | 150-199, 275-299 |
| 035 | 22 | | PA | 16-0 | 21-66-21 | D05060P | | | 10 | | | | D04912J | | 13 | | | 050-099, 162-199 |
| 036 | 22 | | PA | 16-0 | 21-66-21 | D05060P | | | 11 | | | | D04912J | | 14 | | | 050-099, 162-199 |
| 037 | 22 | | PA | 16-0 | 21-66-41 | D05060P | | | 15 | | | | D04912J | | 18 | | | 050-099, 150, 152-199 |
| 038 | 22 | | PA | 16-0 | 21-66-41 | D05060P | | | 19 | | | | D04912J | | 21 | | | 050-099, 150, 152-199 |
| 041 | 22 | | PA | 30-0 | SPARE | D05186P | | | 1 | | | | D04960J | | 10 | | | ALL |
| 201B | 24 | | PL D | 16-0 | 21-31-11 | D04912J | | | 9 | | | | D05060P | | 5 | | | ALL |
| 201R | 24 | | PL D | 0-0 | 21-31-11 | D04912J | | | 10 | | | | D05060P | | 6 | | | ALL |
| 202B | 24 | | PL E | 47-0 | 21-31-11 | D04912J | | | 11 | | | | D04698J | | 6 | | | 050-099 |
| 202B | 24 | | PL E | 56-0 | 21-31-11 | D04912J | | | 11 | | | | D04698J | | 6 | | | 150-199, 275-299 |
| 202R | 24 | | PL E | 0-0 | 21-31-11 | D04912J | | | 12 | | | | D04698J | | 5 | | | ALL |
| 206B | 24 | | PL K | 53-0 | 21-31-21 | D04960J | | | 8 | | | | D04698J | | 8 | | | 050-099 |
| 206B | 24 | | PL K | 62-0 | 21-31-21 | D04960J | | | 8 | | | | D04698J | | 8 | | | 150-199, 275-299 |
| 206R | 24 | | PL K | 0-0 | 21-31-21 | D04960J | | | 9 | | | | D04698J | | 9 | | | ALL |
| 207B | 20 | | PB L | 50-0 | 21-44-22 | D04698J | | | 12 | | | | D05060P | | 8 | | | 050-099 |
| 207B | 20 | | PB L | 60-0 | 21-44-22 | D05060P | | | 8 | | | | D04698J | | 12 | | | 150-199 |
| 207R | 20 | | PB L | 0-0 | 21-44-22 | D04698J | | | 1 | | | | D05060P | | 9 | | | 050-099 |
| 207R | 20 | | PB L | 0-0 | 21-44-22 | D05060P | | | 9 | | | | D04698J | | 1 | | | 150-199 |
| 209B | 22 | | PR II | 16-0 | 21-66-21 | D05060P | | | 13 | | | | D04912J | | 16 | | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W0650

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0654 | 286T0654 | | | AIR COND FEEDER (continued) | | | | | | | | | | | |
| 209R | 22 | | PR | II | 0-0 | 21-66-21 | D05060P | | | | D04912J | | | | 050-099, 162-199 |
| 209Z | | | | II | 0-0 | 21-66-21 | D05060P | | | | D04912J | | | | 050-099, 162-199 |
| 210B | 22 | | PR | IK | 16-0 | 21-66-41 | D05060P | | | | D04912J | | | | 050-099, 150, 152-199 |
| 210R | 22 | | PR | IK | 0-0 | 21-66-41 | D05060P | | | | D04912J | | | | 050-099, 150, 152-199 |
| 210Z | | | | IK | 0-0 | 21-66-41 | D05060P | | | | D04912J | | | | 050-099, 150, 152-199 |
| 401B | 22 | | PT | F | 33-0 | 21-31-11 | D05186P | | | | D04912J | | | | ALL |
| 401G | 22 | | PT | F | 0-0 | 21-31-11 | D05186P | | | | D04912J | | | | ALL |
| 401R | 22 | | PT | F | 0-0 | 21-31-11 | D05186P | | | | D04912J | | | | ALL |
| 401Y | 22 | | PT | F | 0-0 | 21-31-11 | D05186P | | | | D04912J | | | | ALL |
| 401Z | | | | F | 0-0 | 21-31-11 | D05186P | | | | D04912J | | | | ALL |
| 801 | 22 | | PA | | 47-0 | | D04912J | | | | D04698J | | | | 050-099 |
| 801 | 22 | | PA | | 56-0 | SPARE | D04912J | | | | D04698J | | | | 150-199, 275-299 |
| W0655 | 286T0655 | | | CONTRAHELICAL CABLE-CAPT AUDIO SELECT PANEL | | | | | | | | | | | |
| 0BBK | 24 | | P7 | A | 26-0 | 23-51-12 | D00253 | | | | D04601J | | | | ALL |
| 0BBN | 24 | | P7 | A | 0-0 | 23-51-13 | D00253 | | | | D04601J | | | | ALL |
| 0BGK | 24 | | P7 | A | 0-0 | 23-51-13 | D00253 | | | | D04601J | | | | ALL |
| 0BLG | 24 | | P7 | A | 0-0 | 23-51-12 | D00253 | | | | D04601J | | | | ALL |
| 0BLK | 24 | | P7 | A | 0-0 | 23-51-11 | D00253 | | | | D04601J | | | | ALL |
| 0BLU | 24 | | P7 | A | 0-0 | 23-51-11 | D00253 | | | | D04601J | | | | ALL |
| 0BLY | 24 | | P7 | A | 0-0 | 23-51-13 | D00253 | | | | D04601J | | | | ALL |
| 0BOR | 24 | | P7 | A | 0-0 | 23-51-13 | D00253 | | | | D04601J | | | | ALL |
| 0BPR | 24 | | P7 | A | 0-0 | 23-51-12 | D00253 | | | | D04601J | | | | ALL |
| 0BRN | 24 | | P7 | A | 0-0 | 23-51-14 | D00253 | | | | D04601J | | | | ALL |
| 0GRN | 24 | | P7 | A | 0-0 | 23-51-11 | D00253 | | | | D04601J | | | | ALL |
| 0ORG | 24 | | P7 | A | 0-0 | 23-51-13 | D00253 | | | | D04601J | | | | ALL |
| 0PNK | 24 | | P7 | A | 0-0 | 23-51-14 | D00253 | | | | D04601J | | | | ALL |
| 0PUR | 24 | | P7 | A | 0-0 | 23-51-11 | D00253 | | | | D04601J | | | | ALL |
| 0RBK | 24 | | P7 | A | 0-0 | 23-51-14 | D00253 | | | | D04601J | | | | ALL |
| 0RBR | 24 | | P7 | A | 0-0 | 23-51-11 | D00253 | | | | D04601J | | | | ALL |
| 0RGR | 24 | | P7 | A | 0-0 | 23-51-14 | D00253 | | | | D04601J | | | | ALL |
| 0ROR | 24 | | P7 | A | 0-0 | 23-51-14 | D00253 | | | | D04601J | | | | ALL |
| 0RPR | 24 | | P7 | A | 0-0 | 23-51-14 | D00253 | | | | D04601J | | | | ALL |
| 0RYG | 24 | | P7 | A | 0-0 | 23-51-12 | D00253 | | | | D04601J | | | | ALL |
| 0RYL | 24 | | P7 | A | 0-0 | 23-51-14 | D00253 | | | | D04601J | | | | ALL |
| 0UNI | 20 | | P7 | A | 0-0 | 23-51-11 | D00253 | | | | D04601J | | | | ALL |
| 0WBK | 24 | | P7 | A | 0-0 | 23-51-14 | D00253 | | | | D04601J | | | | ALL |
| 0WBN | 24 | | P7 | A | 0-0 | 23-51-11 | D00253 | | | | D04601J | | | | ALL |
| 0WBU | 24 | | P7 | A | 0-0 | 23-51-14 | D00253 | | | | D04601J | | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0650
Page 2
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0655 | 286T0655 | | | CONTRAHELICAL CABLE-CAPT AUDIO SELECT PANEL (continued) | | | | | | | | | | | | |
| 0WBY | 24 | P7 | A | 0-0 | 23-51-11 | D00253 | | 19 | | | | D04601J | 19 | | ALL | |
| 0WGR | 24 | P7 | A | 0-0 | 23-51-14 | D00253 | | 14 | | | | D04601J | 14 | | ALL | |
| 0WHT | 24 | P7 | A | 0-0 | 23-51-14 | D00253 | | 10 | | | | D04601J | 10 | | ALL | |
| 0WOR | 24 | P7 | A | 0-0 | 23-51-14 | D00253 | | 17 | | | | D04601J | 17 | | ALL | |
| 0WPR | 24 | P7 | A | 0-0 | 23-51-14 | D00253 | | 16 | | | | D04601J | 16 | | ALL | |
| 0WRB | 20 | P7 | A | 0-0 | 23-51-11 | D00253 | | 1 | | | | D04601J | 1 | | ALL | |
| 0WRD | 24 | P7 | A | 0-0 | 23-51-14 | D00253 | | 11 | | | | D04601J | 11 | | ALL | |
| 0WYL | 24 | P7 | A | 0-0 | 23-51-14 | D00253 | | 13 | | | | D04601J | 13 | | ALL | |
| 0YBK | 24 | P7 | A | 0-0 | 23-51-12 | D00253 | | 36 | | | | D04601J | 36 | | ALL | |
| 0YEL | 24 | P7 | A | 0-0 | 23-51-11 | D00253 | | 3 | | | | D04601J | 3 | | ALL | |
| 0YGR | 24 | P7 | A | 0-0 | 23-51-12 | D00253 | | 35 | | | | D04601J | 35 | | ALL | |
| 0YOR | 24 | P7 | A | 0-0 | 23-51-13 | D00253 | | 38 | | | | D04601J | 38 | | ALL | |
| 0YPR | 24 | P7 | A | 0-0 | 23-51-12 | D00253 | | 37 | | | | D04601J | 37 | | ALL | |
| W0656 | 286T0656 | | | FUELING, HYDRAULICS, POTABLE WATER FEEDER | | | | | | | | | | | | |
| 001R | 22 | PH | | 47-7 | 26-18-21 | D05068P | | 4 | | | | D05528J | 18 | | 050-099 | |
| 001R | 22 | PH | | 58-4 | 26-18-21 | D05068P | | 4 | | | | D05528J | 18 | | 150-199, 275-299 | |
| 002 | 24 | PK | | 16-4 | SPARE | D04916J | | 16 | | | | D04346P | 5 | | 050-099 | |
| 002 | 24 | PK | | 17-1 | SPARE | D04916J | | 16 | | | | D04346P | 5 | | 150-199, 275-299 | |
| 004 | 22 | PA | | 16-4 | SPARE | D04346P | | 36 | | | | D04916J | 8 | | 050-099 | |
| 004 | 22 | PA | | 17-1 | SPARE | D04346P | | 36 | | | | D04916J | 8 | | 150-199, 275-299 | |
| 005 | 24 | PK | | 16-4 | 29-33-11 | D04346P | | 37 | | | | D04916J | 9 | | 050-099 | |
| 005 | 24 | PK | | 17-1 | 29-33-11 | D04346P | | 37 | | | | D04916J | 9 | | 150-199, 275-299 | |
| 006 | 24 | PK | | 16-4 | 29-33-11 | D04346P | | 45 | | | | D04916J | 10 | | 050-099 | |
| 006 | 24 | PK | | 17-1 | 29-33-11 | D04346P | | 45 | | | | D04916J | 10 | | 150-199, 275-299 | |
| 008 | 22 | PA | | 16-4 | 29-33-11 | D04346P | | 40 | | | | D04916J | 12 | | 050-099 | |
| 008 | 22 | PA | | 17-1 | 29-33-11 | D04346P | | 40 | | | | D04916J | 12 | | 150-199, 275-299 | |
| 009 | 22 | PA | | 57-9 | 30-11-11 | D05840P | | 6 | | | | D05598J | 8 | | 050-099 | |
| 009 | 22 | PA | | 1-2 | 30-11-11 | SM00001 | | | 9 | | | D05598J | 8 | | 150-199, 275-299 | |
| 011 | 22 | PA | | 57-9 | 30-11-11 | D05840P | | 1 | | | | D05598J | 10 | | 050-099 | |
| 011 | 22 | PA | | 67-6 | 30-11-11 | D05840P | | 1 | | | | D05598J | 10 | | 150-199, 275-299 | |
| 012 | 22 | PA | | 57-9 | 30-11-11 | D05840P | | 2 | | | | D05598J | 11 | | 050-099 | |
| 012 | 22 | PA | | 67-6 | 30-11-11 | D05840P | | 2 | | | | D05598J | 11 | | 150-199, 275-299 | |
| 013 | 22 | PA | | 1-2 | SPARE | SM00001 | | | 9 | | | D05598J | 1 | | 150-157 | |
| 013 | 22 | PA | | 1-2 | 30-11-11 | SM00001 | | | 9 | | | D05598J | 1 | | 162-199, 275-299 | |
| 014 | 22 | PA | | 67-6 | SPARE | D05840P | | 3 | | | | D05598J | 7 | | 150-157 | |
| 014 | 22 | PA | | 67-6 | 30-11-11 | D05840P | | 3 | | | | D05598J | 7 | | 275-299 | |
| 015 | 24 | PK | | 57-9 | 30-11-11 | D05840P | | 5 | | | | D05598J | 2 | | 050-099 | |
| 015 | 24 | PK | | 67-6 | 30-11-11 | D05840P | | 5 | | | | D05598J | 2 | | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0650

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0656 | 286T0656 | | | FUELING, HYDRAULICS, POTABLE WATER FEEDER (continued) | | | | | | | | | | | |
| 017 | 22 | | PA | | 66-11 | 30-11-11 | SM00001 | | | 9 | D05840P | | 6 | | 150-199, 275-299 |
| 018 | 20 | | PA | | 3-11 | 32-41-11 | D04954J | | | 3 | GD04168 | A.. | 2 | | 050-099 |
| 018 | 20 | | PA | | 4-0 | 32-41-11 | D04954J | | | 3 | GD04168 | A.. | 2 | | 150-199, 275-299 |
| 019 | 22 | | PA | | 64-6 | 32-42-11 | D05066J | | | 2 | D04278J | | 2 | | 050-099 |
| 019 | 22 | | PA | | 74-7 | 32-42-11 | D05066J | | | 2 | D04278J | | 2 | | 150-199, 275-299 |
| 020 | 22 | | PA | | 64-6 | 32-42-11 | D05066J | | | 3 | D04278J | | 3 | | 050-099 |
| 020 | 22 | | PA | | 74-7 | 32-42-11 | D05066J | | | 3 | D04278J | | 3 | | 150-199, 275-299 |
| 021 | 22 | | PA | | 64-6 | 32-42-11 | D05066J | | | 4 | D04278J | | 4 | | 050-099 |
| 021 | 22 | | PA | | 74-7 | 32-42-11 | D05066J | | | 4 | D04278J | | 4 | | 150-199, 275-299 |
| 022 | 20 | | PA | | 7-2 | 32-42-11 | GD00854 | D.. | 2 | | D04278J | | 5 | | 050-099 |
| 022 | 20 | | PA | | 7-0 | 32-42-11 | GD00854 | D.. | 2 | | D04278J | | 5 | | 150-199, 275-299 |
| 023 | 20 | | PA | | 7-2 | 32-42-11 | GD00854 | D.. | 2 | | D04278J | | 6 | | 050-099 |
| 023 | 20 | | PA | | 7-0 | 32-42-11 | GD00854 | D.. | 2 | | D04278J | | 6 | | 150-199, 275-299 |
| 024 | 20 | | PA | | 7-2 | 32-42-11 | GD00854 | D.. | 2 | | D04278J | | 7 | | 050-099 |
| 024 | 20 | | PA | | 7-0 | 32-42-11 | GD00854 | D.. | 2 | | D04278J | | 7 | | 150-199, 275-299 |
| 029 | 22 | | PA | | 47-6 | 29-11-22 | D04346P | | | 41 | D05528J | | 9 | | 050-099 |
| 029 | 22 | | PA | | 58-1 | 29-11-22 | D04346P | | | 41 | D05528J | | 9 | | 150-199, 275-299 |
| 031R | 22 | | PH | | 65-10 | 26-17-11 | D05068P | | | 23 | D04954J | | 18 | | 050-099 |
| 031R | 22 | | PH | | 76-6 | 26-17-11 | D05068P | | | 23 | D04954J | | 18 | | 150-199, 275-299 |
| 032R | 22 | | PH | | 27-4 | 26-17-11 | SP01522 | | | 9 | D04954J | | 19 | | 050-099 |
| 032R | 22 | | PH | | 27-5 | 26-17-11 | SP01522 | | | 9 | D04954J | | 19 | | 150-199, 275-299 |
| 033 | 22 | | PA | | 65-9 | 32-41-11 | D04346P | | | 1 | D04954J | | 1 | | 050-099 |
| 033 | 22 | | PA | | 76-4 | 32-41-11 | D04346P | | | 1 | D04954J | | 1 | | 150-199, 275-299 |
| 034 | 22 | | PA | | 65-9 | 32-41-11 | D04346P | | | 2 | D04954J | | 2 | | 050-099 |
| 034 | 22 | | PA | | 76-4 | 32-41-11 | D04346P | | | 2 | D04954J | | 2 | | 150-199, 275-299 |
| 035 | 20 | | PA | | 64-6 | 32-41-11 | D04346P | | | 3 | GD04168 | A.. | 2 | | 050-099 |
| 035 | 20 | | PA | | 75-0 | 32-41-11 | D04346P | | | 3 | GD04168 | A.. | 2 | | 150-199, 275-299 |
| 036 | 24 | | PK | | 47-7 | 29-32-11 | D05068P | | | 19 | D05528J | | 14 | | 050-099 |
| 036 | 24 | | PK | | 58-4 | 29-32-11 | D05068P | | | 19 | D05528J | | 14 | | 150-199, 275-299 |
| 037 | 24 | | PK | | 47-7 | 29-32-11 | D05068P | | | 20 | D05528J | | 15 | | 050-099 |
| 037 | 24 | | PK | | 58-4 | 29-32-11 | D05068P | | | 20 | D05528J | | 15 | | 150-199, 275-299 |
| 038 | 22 | | PA | | 68-9 | 32-42-12 | D05066J | | | 6 | D04770J | | 2 | | 050-099 |
| 038 | 20 | | PA | | 78-9 | 32-42-12 | D05066J | | | 6 | D04770J | | 2 | | 150-199 |
| 038 | 22 | | PA | | 78-9 | 32-42-12 | D05066J | | | 6 | D04770J | | 2 | | 275-299 |
| 039 | 22 | | PA | | 68-9 | 32-42-12 | D05066J | | | 5 | D04770J | | 3 | | 050-099 |
| 039 | 22 | | PA | | 78-9 | 32-42-12 | D05066J | | | 5 | D04770J | | 3 | | 150-199, 275-299 |
| 042 | 20 | | PA | | 4-3 | 32-42-12 | GD00854 | D.. | 2 | | D04954J | | 7 | | ALL |
| 043 | 22 | | PA | | 64-6 | 32-42-12 | D05066J | | | 10 | D04954J | | 8 | | 050-099 |
| 043 | 22 | | PA | | 74-5 | 32-42-12 | D05066J | | | 10 | D04954J | | 8 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11
Section W0650
Page 4
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0656 | 286T0656 | | | FUELING, HYDRAULICS, POTABLE WATER FEEDER (continued) | | | | | | | | | | | | | |
| 044 | 22 | PA | | 64-6 | 32-42-12 | D05066J | | 11 | | | | | D04954J | 9 | | | 050-099 |
| 044 | 22 | PA | | 74-5 | 32-42-12 | D05066J | | 11 | | | | | D04954J | 9 | | | 150-199, 275-299 |
| 045 | 22 | PA | | 64-6 | 32-42-12 | D05066J | | 12 | | | | | D04954J | 10 | | | 050-099 |
| 045 | 22 | PA | | 74-5 | 32-42-12 | D05066J | | 12 | | | | | D04954J | 10 | | | 150-199, 275-299 |
| 047 | 20 | PA | | 4-3 | 32-42-12 | GD00854 | | D.. | 2 | | | | D04954J | 12 | | | ALL |
| 048 | 22 | PA | | 64-6 | 32-42-12 | D05066J | | 13 | | | | | D04954J | 13 | | | 050-099 |
| 048 | 22 | PA | | 74-5 | 32-42-12 | D05066J | | 13 | | | | | D04954J | 13 | | | 150-199, 275-299 |
| 049 | 20 | PA | | 49-4 | 33-42-21 | D05068P | | 21 | | | | | D02114 | 3 | | | 050-099 |
| 049 | 18 | PA | | 60-11 | 33-42-21 | D05068P | | 36 | DL | | | | D02114 | 3 | | | 150-199, 275-299 |
| 050 | 18 | PA | | 47-8 | 33-44-21 | D05068P | | 1 | DL | | | | D05598J | 6 | DK | | 050-099 |
| 050 | 18 | PA | | 58-4 | 33-44-21 | D05068P | | 1 | DL | | | | D05598J | 6 | DK | | 150-199, 275-299 |
| 051 | 22 | PA | | 65-10 | 29-11-31 | D05068P | | 14 | | | | | D04954J | 14 | | | 050-099 |
| 051 | 22 | PA | | 76-6 | 29-11-31 | D05068P | | 14 | | | | | D04954J | 14 | | | 150-199, 275-299 |
| 052 | 20 | PA | | 4-3 | 29-11-31 | GD00854 | | D.. | 2 | | | | D04954J | 15 | | | ALL |
| 053 | 22 | PQ | A | 44-6 | 29-33-11 | D04916J | | 15 | | | | | D05528J | 47 | | | 050-099 |
| 053 | 22 | PQ | A | 54-7 | 29-33-11 | D04916J | | 15 | | | | | D05528J | 47 | | | 150-199, 275-299 |
| 053Z | | | A | 0-0 | 29-33-11 | D04916J | | | | | FB | | D05528J | | | FA | ALL |
| 054 | 22 | PA | | 44-6 | 29-33-11 | D04916J | | 2 | | | | | D05528J | 19 | | | 050-099 |
| 054 | 22 | PA | | 54-7 | 29-33-11 | D04916J | | 2 | | | | | D05528J | 19 | | | 150-199, 275-299 |
| 055 | 22 | PA | | 44-6 | 29-33-11 | D04916J | | 3 | | | | | D05528J | 20 | | | 050-099 |
| 055 | 22 | PA | | 54-7 | 29-33-11 | D04916J | | 3 | | | | | D05528J | 20 | | | 150-199, 275-299 |
| 056 | 22 | PA | | 44-6 | 29-33-11 | D04916J | | 6 | | | | | D05528J | 17 | | | 050-099 |
| 056 | 22 | PA | | 54-7 | 29-33-11 | D04916J | | 6 | | | | | D05528J | 17 | | | 150-199, 275-299 |
| 057 | 22 | PA | | 65-9 | 29-31-11 | D04346P | | 7 | | | | | D04278J | 15 | | | 050-099 |
| 057 | 22 | PA | | 76-6 | 29-31-11 | D04346P | | 7 | | | | | D04278J | 15 | | | 150-199, 275-299 |
| 060 | 16 | PA | | 5-1 | 33-42-21 | D02114 | | 1 | | | | | GD03558 | A.. | 2 | | ALL |
| 061 | 16 | PA | | 5-1 | 33-42-21 | D02114 | | 6 | | | | | GD03558 | S.. | 2 | | ALL |
| 062 | 16 | PA | | 15-8 | 33-42-21 | D02114 | | 5 | | | | | L00116 | =P | M | | 050-099 |
| 062 | 16 | PA | | 15-9 | 33-42-21 | D02114 | | 5 | | | | | L00116 | =P | M | | 150-199, 275-299 |
| 063 | 16 | PA | | 3-4 | 33-42-21 | GD03560 | | A.. | N | | | | L00116 | =G | M | | 050-099 |
| 063 | 16 | PA | | 3-5 | 33-42-21 | GD03560 | | A.. | N | | | | L00116 | =G | M | | 150-199, 275-299 |
| 064 | 18 | PA | | 58-4 | SPARE | D05598J | | 14 | DK | | | | D05068P | CAP | Y | | 150-155, 162-165, 275-276 |
| 064 | 18 | PA | | 58-4 | SPARE | D05598J | | 14 | DK | | | | D05068P | 39 | DL | | 156-157, 166-199 |
| 064 | 18 | PA | | 58-4 | SPARE | D05598J | | 14 | DK | | | | D05068P | 21 | DL | | 277-299 |
| 065 | 24 | PK | | 58-4 | SPARE | D05598J | | 13 | | | | | D05068P | 2 | | | 150-199, 275-299 |
| 066 | 22 | PA | | 67-6 | SPARE | D05598J | | 16 | | | | | D05840P | CAP | Y | | 150-199, 275-299 |
| 070 | 20 | PA | | 47-7 | 33-43-11 | D04346P | | 9 | | | | | D05598J | 4 | | | 050-099 |
| 070 | 16 | PA | | 58-1 | 33-43-11 | D04346P | | 9 | FL | | | | D05598J | 3 | FM | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0650

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0656 | 286T0656 | | | FUELING, HYDRAULICS, POTABLE WATER FEEDER (continued) | | | | | | | | | | | | |
| 072 | 22 | PA | | | 47-7 | 29-32-11 | D05528J | | 22 | | | | | | | 050-099 |
| 072 | 22 | PA | | | 58-4 | 29-32-11 | D05528J | | 22 | | | | | | | 150-199, 275-299 |
| 074 | 18 | PA | | | 49-1 | 33-42-11 | D04346P | | 21 | DL | | T00130 | HV3 | E | | 050-099 |
| 074 | 16 | PA | | | 60-11 | 33-42-11 | D04346P | | 21 | FL | | T00130 | HV3 | E | | 150-199, 275-299 |
| 075 | 20 | PA | | | 49-1 | 33-42-11 | D04346P | | 15 | | | T00130 | HV1 | E | | 050-099 |
| 075 | 16 | PA | | | 60-11 | 33-42-11 | D04346P | | 15 | FL | | T00130 | HV1 | E | | 150-199, 275-299 |
| 076 | 12 | PA | | | 3-9 | 33-42-11 | GD01494 | | A.. | E | | T00130 | GND | E | | 050-099 |
| 076 | 12 | PA | | | 4-6 | 33-42-11 | GD01494 | | A.. | E | | T00130 | GND | E | | 150-199, 275-299 |
| 077 | 12 | PA | | | 15-5 | 33-42-11 | L00112 | | =P | M | | T00130 | LV | E | | 050-099 |
| 077 | 12 | PA | | | 16-0 | 33-42-11 | L00112 | | =P | M | | T00130 | LV | E | | 150-199, 275-299 |
| 078 | 12 | PA | | | 3-1 | 33-42-11 | L00112 | | =G | M | | GD01448 | A.. | N | | 050-099 |
| 078 | 12 | PA | | | 3-2 | 33-42-11 | L00112 | | =G | M | | GD01448 | A.. | N | | 150-199, 275-299 |
| 079 | 24 | PK | | | 47-6 | 36-11-62 | D04346P | | 48 | | | D05528J | | | | 050-099 |
| 079 | 24 | PK | | | 58-1 | 36-11-62 | D04346P | | 48 | | | D05528J | | | | 150-199, 275-299 |
| 080 | 24 | PK | | | 47-6 | 36-11-62 | D04346P | | 47 | | | D05528J | | | | 050-099 |
| 080 | 24 | PK | | | 58-1 | 36-11-62 | D04346P | | 47 | | | D05528J | | | | 150-199, 275-299 |
| 081 | 24 | PK | | | 47-7 | 36-11-52 | D05068P | | 27 | | | D05528J | | | | 050-099 |
| 081 | 24 | PK | | | 58-4 | 36-11-52 | D05068P | | 27 | | | D05528J | | | | 150-199, 275-299 |
| 082 | 18 | PA | | | 47-7 | SPARE | D05068P | | 28 | DL | | D05528J | 4 | DK | | 050-099 |
| 082 | 18 | PA | | | 58-4 | SPARE | D05068P | | 28 | DL | | D05528J | 4 | DK | | 150-199, 275-299 |
| 083 | 24 | PK | | | 47-7 | 36-11-52 | D05068P | | 29 | | | D05528J | 49 | | | 050-099 |
| 083 | 24 | PK | | | 58-4 | 36-11-52 | D05068P | | 29 | | | D05528J | 49 | | | 150-199, 275-299 |
| 084 | 24 | PK | | | 47-6 | 36-23-21 | D04346P | | 27 | | | D05528J | 30 | | | 050-099 |
| 084 | 24 | PK | | | 58-1 | SPARE | D04346P | | 27 | | | D05528J | 30 | | | 150-154, 275 |
| 084 | 24 | PK | | | 58-1 | 36-23-21 | D04346P | | 27 | | | D05528J | 30 | | | 155-199, 276-299 |
| 085 | 24 | PK | | | 47-7 | 36-11-52 | D05068P | | 31 | | | D05528J | 50 | | | 050-099 |
| 085 | 24 | PK | | | 58-4 | 36-11-52 | D05068P | | 31 | | | D05528J | 50 | | | 150-199, 275-299 |
| 086 | 18 | PA | | | 47-7 | 36-11-52 | D05068P | | 32 | DL | | D05528J | 27 | DK | | 050-099 |
| 086 | 18 | PA | | | 58-4 | 36-11-52 | D05068P | | 32 | DL | | D05528J | 27 | DK | | 150-199, 275-299 |
| 087 | 18 | PA | | | 47-7 | 36-11-52 | D05068P | | 33 | DL | | D05528J | 26 | DK | | 050-099 |
| 087 | 18 | PA | | | 58-4 | 36-11-52 | D05068P | | 33 | DL | | D05528J | 26 | DK | | 150-199, 275-299 |
| 088 | 24 | PK | | | 47-7 | 36-11-52 | D05068P | | 34 | | | D05528J | 24 | | | 050-099 |
| 088 | 24 | PK | | | 58-4 | 36-11-52 | D05068P | | 34 | | | D05528J | 24 | | | 150-199, 275-299 |
| 089 | 22 | PA | | | 47-6 | 36-22-11 | D04346P | | 6 | | | D05528J | 23 | | | 050-099 |
| 089 | 22 | PA | | | 58-1 | 36-22-11 | D04346P | | 6 | | | D05528J | 23 | | | 150-199, 275-299 |
| 090 | 24 | PK | | | 47-6 | 36-11-62 | D04346P | | 12 | | | D05528J | 1 | | | 050-099 |
| 090 | 24 | PK | | | 58-1 | 36-11-62 | D04346P | | 12 | | | D05528J | 1 | | | 150-199, 275-299 |
| 091 | 24 | PK | | | 47-6 | 36-11-62 | D04346P | | 13 | | | D05528J | 2 | | | 050-099 |
| 091 | 24 | PK | | | 58-1 | 36-11-62 | D04346P | | 13 | | | D05528J | 2 | | | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0650
Page 6
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0656 | 286T0656 | | | FUELING, HYDRAULICS, POTABLE WATER FEEDER (continued) | | | | | | | | | | | | |
| 092 | 18 | | PA | 47-6 | 36-11-62 | D04346P | 16 | DL | | | | D05528J | 3 | DK | | 050-099 |
| 092 | 18 | | PA | 58-1 | 36-11-62 | D04346P | 16 | DL | | | | D05528J | 3 | DK | | 150-199, 275-299 |
| 093 | 18 | | PA | 47-6 | 36-11-62 | D04346P | 17 | DL | | | | D05528J | 5 | DK | | 050-099 |
| 093 | 18 | | PA | 58-1 | 36-11-62 | D04346P | 17 | DL | | | | D05528J | 5 | DK | | 150-199, 275-299 |
| 094 | 24 | | PK | 47-6 | 36-11-62 | D04346P | 18 | | | | | D05528J | 6 | | | 050-099 |
| 094 | 24 | | PK | 58-1 | 36-11-62 | D04346P | 18 | | | | | D05528J | 6 | | | 150-199, 275-299 |
| 095 | 24 | | PK | 47-6 | 36-11-62 | D04346P | 19 | | | | | D05528J | 7 | | | 050-099 |
| 095 | 24 | | PK | 58-1 | 36-11-62 | D04346P | 19 | | | | | D05528J | 7 | | | 150-199, 275-299 |
| 096 | 24 | | PK | 47-6 | 36-11-62 | D04346P | 20 | | | | | D05528J | 8 | | | 050-099 |
| 096 | 24 | | PK | 58-1 | 36-11-62 | D04346P | 20 | | | | | D05528J | 8 | | | 150-199, 275-299 |
| 098 | 24 | | PK | 47-6 | 36-11-62 | D04346P | 22 | | | | | D05528J | 10 | | | 050-099 |
| 098 | 24 | | PK | 58-1 | 36-11-62 | D04346P | 22 | | | | | D05528J | 10 | | | 150-199, 275-299 |
| 100 | 24 | | PK | 47-6 | 36-23-21 | D04346P | 24 | | | | | D05528J | 44 | | | 050-099 |
| 100 | 24 | | PK | 58-1 | 36-23-21 | D04346P | 24 | | | | | D05528J | 44 | | | 150-199, 275-299 |
| 101 | 24 | | PK | 47-6 | 36-23-21 | D04346P | 25 | | | | | D05528J | 37 | | | 050-099 |
| 101 | 24 | | PK | 58-1 | 36-23-21 | D04346P | 25 | | | | | D05528J | 37 | | | 150-199, 275-299 |
| 102 | 24 | | PK | 47-6 | 36-23-21 | D04346P | 26 | | | | | D05528J | 31 | | | 050-099 |
| 102 | 24 | | PK | 58-1 | 36-23-21 | D04346P | 26 | | | | | D05528J | 31 | | | 150-199, 275-299 |
| 103 | 24 | | PK | 47-6 | 36-23-21 | D04346P | 28 | | | | | D05528J | 32 | | | 050-099 |
| 103 | 24 | | PK | 58-1 | 36-23-21 | D04346P | 28 | | | | | D05528J | 32 | | | 150-199, 275-299 |
| 104 | 22 | | PA | 65-9 | 28-42-11 | D04346P | 33 | | | | | D04278J | 18 | | | 050-099 |
| 104 | 22 | | PA | 76-6 | 28-42-11 | D04346P | 33 | | | | | D04278J | 18 | | | 150-199, 275-299 |
| 106 | 22 | | PA | 65-9 | SPARE | D04346P | 34 | | | | | D04278J | 19 | | | 050-099 |
| 106 | 22 | | PA | 76-6 | SPARE | D04346P | 34 | | | | | D04278J | 19 | | | 150-199, 275-278 |
| 106 | 22 | | PA | 76-6 | 28-42-31 | D04346P | 34 | | | | | D04278J | 19 | | | 280-299 |
| 109 | 16 | | PA | 44-2 | 25-65-12 | SP02564 | | | | S | | D04278J | 8 | | | 050-099 |
| 109 | 16 | | PA | 44-3 | 25-65-12 | SP02564 | | | | S | | D04278J | 8 | | | 150-199, 275-299 |
| 110 | 24 | | PK | 13-10 | 36-11-41 | D05840P | 13 | | | | | D05068P | 5 | | | 050-099 |
| 110 | 24 | | PK | 13-9 | 36-11-41 | D05840P | 13 | | | | | D05068P | 5 | | | 150-199, 275-299 |
| 111 | 24 | | PK | 13-10 | 36-11-41 | D05840P | 14 | | | | | D05068P | 6 | | | 050-099 |
| 111 | 24 | | PK | 13-9 | 36-11-41 | D05840P | 14 | | | | | D05068P | 6 | | | 150-199, 275-299 |
| 112 | 24 | | PK | 13-10 | 36-11-41 | D05840P | 15 | | | | | D05068P | 7 | | | 050-099 |
| 112 | 24 | | PK | 13-9 | 36-11-41 | D05840P | 15 | | | | | D05068P | 7 | | | 150-199, 275-299 |
| 113 | 24 | | PK | 13-10 | 36-11-41 | D05840P | 16 | | | | | D05068P | 8 | | | 050-099 |
| 113 | 24 | | PK | 13-9 | 36-11-41 | D05840P | 16 | | | | | D05068P | 8 | | | 150-199, 275-299 |
| 128 | 16 | | PA | 7-2 | 25-65-12 | D04278J | 9 | | | | | GD00854 | D.. | 2 | | 050-099 |
| 128 | 16 | | PA | 7-0 | 25-65-12 | D04278J | 9 | | | | | GD00854 | D.. | 2 | | 150-199, 275-299 |
| 130 | 24 | | PK | 16-4 | 24-11-21 | D04346P | 38 | | | | | D04916J | 18 | | | 050-099 |
| 130 | 24 | | PK | 17-1 | 24-11-21 | D04346P | 38 | | | | | D04916J | 18 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0650

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0656 | 286T0656 | | | FUELING, HYDRAULICS, POTABLE WATER FEEDER (continued) | | | | | | | | | | | | | |
| 131 | 24 | | PK | 16-4 | 24-11-21 | D04346P | | 39 | | | | | D04916J | 17 | | | 050-099 |
| 131 | 24 | | PK | 17-1 | 24-11-21 | D04346P | | 39 | | | | | D04916J | 17 | | | 150-199, 275-299 |
| 141 | 20 | | PA | 67-4 | 29-11-31 | D06280J | | 1 | | | | | D04916J | 1 | | | 050-099 |
| 141 | 20 | | PA | 77-4 | 29-11-31 | D06280J | | 1 | | | | | D04916J | 1 | | | 150-199, 275-299 |
| 144 | 20 | | PA | 67-4 | 29-11-31 | D04916J | | 13 | | | | | D06280J | 4 | | | 050-099 |
| 144 | 20 | | PA | 77-4 | 29-11-31 | D04916J | | 13 | | | | | D06280J | 4 | | | 150-199, 275-299 |
| 145 | 22 | | PA | 64-6 | SPARE | D05066J | | 7 | | | | | D04278J | 10 | | | 050-099 |
| 145 | 22 | | PA | 74-7 | SPARE | D05066J | | 7 | | | | | D04278J | 10 | | | 150-199, 275-299 |
| 147 | 20 | | PA | 11-10 | 29-11-31 | D06280J | | 7 | | | | | GD00854 | D.. | 2 | | ALL |
| 160 | 24 | | PK | 47-7 | 36-11-62 | D05528J | | 13 | | | | | D05068P | 13 | | | 050-099 |
| 160 | 24 | | PK | 58-4 | 36-11-62 | D05528J | | 13 | | | | | D05068P | 13 | | | 150-199, 275-299 |
| 161 | 24 | | PK | 47-8 | 36-11-62 | D05598J | | 23 | | | | | D05068P | 16 | | | 050-099 |
| 161 | 24 | | PK | 58-4 | 36-11-62 | D05598J | | 23 | | | | | D05068P | 16 | | | 150-199, 275-299 |
| 162 | 18 | | PA | 47-8 | 36-11-62 | D05598J | | 24 | DK | | | | D05068P | 24 | DL | | 050-099 |
| 162 | 18 | | PA | 58-4 | 36-11-62 | D05598J | | 24 | DK | | | | D05068P | 24 | DL | | 150-199, 275-299 |
| 163 | 18 | | PA | 47-8 | 36-11-62 | D05598J | | 25 | DK | | | | D05068P | 25 | DL | | 050-099 |
| 163 | 18 | | PA | 58-4 | 36-11-62 | D05598J | | 25 | DK | | | | D05068P | 25 | DL | | 150-199, 275-299 |
| 173 | 20 | | PA | 66-1 | 28-31-11 | D05068P | | 11 | | | | | D08376J | 1 | | | 050-099 |
| 173 | 20 | | PA | 76-9 | 28-31-11 | D05068P | | 11 | | | | | D08376J | 1 | | | 155-199, 276-299 |
| 174 | 20 | | PA | 66-1 | 28-31-11 | D05068P | | 38 | | | | | D08376J | 2 | | | 050-099 |
| 174 | 20 | | PA | 76-9 | 28-31-11 | D05068P | | 38 | | | | | D08376J | 2 | | | 155-199, 276-299 |
| 175 | 20 | | PA | 66-1 | 28-31-11 | D05068P | | 37 | | | | | D08376J | 3 | | | 050-099 |
| 175 | 20 | | PA | 76-9 | 28-31-11 | D05068P | | 37 | | | | | D08376J | 3 | | | 155-199, 276-299 |
| 176 | 20 | | PA | 66-1 | 28-31-12 | D05068P | | 40 | | | | | D08376J | 4 | | | 050-099 |
| 176 | 20 | | PA | 76-9 | 28-31-12 | D05068P | | 40 | | | | | D08376J | 4 | | | 155-199, 276-299 |
| 177 | 20 | | PA | 66-1 | 28-31-12 | D05068P | | 41 | | | | | D08376J | 5 | | | 050-099 |
| 177 | 20 | | PA | 76-9 | 28-31-12 | D05068P | | 41 | | | | | D08376J | 5 | | | 155-199, 276-299 |
| 178 | 20 | | PA | 66-1 | 28-31-12 | D05068P | | 42 | | | | | D08376J | 6 | | | 050-099 |
| 178 | 20 | | PA | 76-9 | 28-31-12 | D05068P | | 42 | | | | | D08376J | 6 | | | 155-199, 276-299 |
| 179 | 20 | | PQ | HD | 66-1 | 28-42-13 | | 43 | | | | | D08376J | 7 | | | 050-099 |
| 179 | 20 | | PQ | HD | 76-9 | 28-42-13 | | 43 | | | | | D08376J | 7 | | | 155-199, 276-299 |
| 179Z | | | | HD | 0-0 | 28-42-13 | | DED | | | | | D08376J | DED | | | 050-099, 155-199, 276-299 |
| 184 | 24 | | PK | 57-5 | 78-36-21 | D07040J | | 3 | | | | | D05840P | 8 | | | 050-099 |
| 184 | 24 | | PK | 67-6 | 78-36-21 | D07040J | | 3 | | | | | D05840P | 8 | | | 150-166, 275-276, 280-299 |
| 184 | 24 | | PK | 67-6 | 78-36-21 | D05840P | | 8 | | | | | D07040J | 3 | | | 167-199, 277-278 |
| 185 | 20 | | PA | 8-0 | 78-36-21 | GD01316 | | S.. | E | | | | D05840P | | | FZ | 050-099, 150-166, 275-276, 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0650
Page 8
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0656 | 286T0656 | | | FUELING, HYDRAULICS, POTABLE WATER FEEDER (continued) | | | | | | | | | | | | |
| 185 | 20 | | PA | 8-0 | 78-36-21 | D05840P | | | | FZ | GD01316 | S.. | E | | 167-199, 277-278 | |
| 188 | 24 | | PK | 47-8 | 36-11-62 | D05068P | | 26 | | | D05598J | 17 | | | 050-099 | |
| 188 | 24 | | PK | 58-4 | 36-11-62 | D05068P | | 26 | | | D05598J | 17 | | | 150-199, 275-299 | |
| 189 | 24 | | PK | 47-8 | 36-11-62 | D05068P | | 12 | | | D05598J | 18 | | | 050-099 | |
| 189 | 24 | | PK | 58-4 | 36-11-62 | D05068P | | 12 | | | D05598J | 18 | | | 150-199, 275-299 | |
| 190 | 24 | | PK | 47-8 | 36-11-62 | D05068P | | 15 | | | D05598J | 19 | | | 050-099 | |
| 190 | 24 | | PK | 58-4 | 36-11-62 | D05068P | | 15 | | | D05598J | 19 | | | 150-199, 275-299 | |
| 191 | 24 | | PK | 47-6 | 36-11-62 | D05528J | | 55 | | | D04346P | 49 | | | 050-099 | |
| 191 | 24 | | PK | 58-1 | 36-11-62 | D05528J | | 55 | | | D04346P | 49 | | | 150-155, 162-165, 275-276 | |
| 191 | 24 | | PK | 58-1 | 36-11-62 | D04346P | | 49 | | | D05528J | 55 | | | 156-157, 166-199, 277-299 | |
| 192B | 24 | | PL AT | 47-6 | 36-11-62 | D05528J | | 53 | | | D04346P | 35 | | | 050-099 | |
| 192B | 24 | | PL AT | 58-1 | 36-11-62 | D05528J | | 53 | | | D04346P | 35 | | | 150-155, 162-165, 275-276 | |
| 192B | 24 | | PL AT | 58-1 | 36-11-62 | D04346P | | 35 | | | D05528J | 53 | | | 156-157, 166-199, 277-299 | |
| 192R | 24 | | PL AT | 0-0 | 36-11-62 | D05528J | | 54 | | | D04346P | 55 | | | 050-099, 150-155, 162-165, 275-276 | |
| 192R | 24 | | PL AT | 0-0 | 36-11-62 | D04346P | | 55 | | | D05528J | 54 | | | 156-157, 166-199, 277-299 | |
| 193 | 18 | | PQ S | 57-5 | 78-36-21 | D07040J | | 1 | | | D05840P | 7 | DL | | 050-099 | |
| 193 | 18 | | PQ S | 67-6 | 78-36-21 | D07040J | | 1 | | | D05840P | 7 | DL | | 150-166, 275-276, 280-299 | |
| 193 | 18 | | PQ S | 67-6 | 78-36-21 | D05840P | | 7 | DL | | D07040J | 1 | | | 167-199, 277-278 | |
| 193Z | | | S | 0-0 | 78-36-21 | D07040J | | =CC | D | | D05840P | | | FZ | 050-099, 150-166, 275-276, 280-299 | |
| 193Z | | | S | 0-0 | 78-36-21 | D05840P | | | | FZ | D07040J | =CC | D | | 167-199, 277-278 | |
| 194 | 18 | | PQ R | 57-5 | 78-36-21 | D07040J | | 2 | | | D05840P | REF | DL | | 050-099 | |
| 194 | 18 | | PQ R | 67-6 | 78-36-21 | D07040J | | 2 | | | D05840P | REF | DL | | 150-166, 275-276, 280-299 | |
| 194 | 18 | | PQ R | 67-6 | 78-36-21 | D05840P | | REF | DL | | D07040J | 2 | | | 167-199, 277-278 | |
| 194Z | | | R | 0-0 | 78-36-21 | D07040J | | =CC | D | | D05840P | | | FZ | 050-099, 150-166, 275-276, 280-299 | |
| 194Z | | | R | 0-0 | 78-36-21 | D05840P | | | | FZ | D07040J | =CC | D | | 167-199, 277-278 | |
| 201B | 22 | | PR D | 64-6 | 32-42-12 | D05066J | | 8 | | | D04954J | 5 | | | 050-099 | |
| 201B | 22 | | PR D | 74-5 | 32-42-12 | D05066J | | 8 | | | D04954J | 5 | | | 150-199, 275-299 | |
| 201R | 22 | | PR D | 0-0 | 32-42-12 | D05066J | | 9 | | | D04954J | 6 | | | ALL | |
| 201Z | | | D | 0-0 | 32-42-12 | D05066J | | 14 | | | D04954J | 16 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0650

Page 9

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|-------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0656 | 286T0656 | | | FUELING, HYDRAULICS, POTABLE WATER FEEDER (continued) | | | | | | | | | | | |
| 202B | 20 | PB | IB | 47-6 | 36-22-21 | D04346P | 53 | | | D05528J | 45 | | | 050-099 | |
| 202B | 20 | PB | IA | 58-1 | 36-22-21 | D04346P | 53 | | | D05528J | 45 | | | 150-199, 275-299 | |
| 202R | 20 | PB | IB | 0-0 | 36-22-21 | D04346P | 52 | | | D05528J | 46 | | | 050-099 | |
| 202R | 20 | PB | IA | 0-0 | 36-22-21 | D04346P | 52 | | | D05528J | 46 | | | 150-199, 275-299 | |
| 204B | 22 | PB | B | 65-9 | 29-31-11 | D04346P | 4 | | | D04278J | 17 | | | 050-099 | |
| 204B | 22 | PB | B | 76-6 | 29-31-11 | D04346P | 4 | | | D04278J | 17 | | | 150-199, 275-299 | |
| 204R | 22 | PB | B | 0-0 | 29-31-11 | D04346P | 8 | | | D04278J | 16 | | | ALL | |
| 205B | 24 | PL | E | 58-4 | SPARE | D05598J | 20 | | | D05068P | 10 | | | 150-199, 275-299 | |
| 205R | 24 | PL | E | 0-0 | SPARE | D05598J | 21 | | | D05068P | 11 | | | 150-154, 275 | |
| 205R | 24 | PL | E | 0-0 | SPARE | D05598J | 21 | | | D05068P | CAP | Y | | 155, 162-165, 276 | |
| 205R | 24 | PL | E | 0-0 | SPARE | D05598J | 21 | | | D05068P | 9 | | | 156-157, 166-199 | |
| 205R | 24 | PL | E | 0-0 | SPARE | D05598J | 21 | | | D05068P | 17 | | | 277-299 | |
| 206B | 22 | PB | F | 58-4 | SPARE | D05068P | 40 | | | D05598J | 22 | | | 150-154 | |
| 206B | 22 | PB | F | 58-4 | SPARE | D05068P | 35 | | | D05598J | 22 | | | 155-199 | |
| 206B | 22 | PB | F | 58-4 | SPARE | D05068P | 3 | | | D05598J | 22 | | | 275-299 | |
| 206R | 22 | PB | F | 0-0 | SPARE | D05068P | 39 | | | D05598J | 9 | | | 150-155, 162-165 | |
| 206R | 22 | PB | F | 0-0 | SPARE | D05068P | 21 | | | D05598J | 9 | | | 156-157, 166-199 | |
| 206R | 22 | PB | F | 0-0 | SPARE | D05068P | CAP | Y | | D05598J | 9 | | | 275-276 | |
| 206R | 22 | PB | F | 0-0 | SPARE | D05068P | 9 | | | D05598J | 9 | | | 277-299 | |
| 207B | 24 | PL | G | 58-4 | SPARE | D05068P | 42 | | | D05598J | 26 | | | 150-154 | |
| 207B | 24 | PL | G | 58-4 | SPARE | D05068P | 17 | | | D05598J | 26 | | | 155-199 | |
| 207B | 24 | PL | G | 58-4 | SPARE | D05068P | 9 | | | D05598J | 26 | | | 275-276 | |
| 207B | 24 | PL | G | 58-4 | SPARE | D05068P | 35 | | | D05598J | 26 | | | 277-299 | |
| 207R | 24 | PL | G | 0-0 | SPARE | D05068P | 41 | | | D05598J | 27 | | | 150-154 | |
| 207R | 24 | PL | G | 0-0 | SPARE | D05068P | CAP | Y | | D05598J | 27 | | | 155, 162-165 | |
| 207R | 24 | PL | G | 0-0 | SPARE | D05068P | 3 | | | D05598J | 27 | | | 156-157, 166-199 | |
| 207R | 24 | PL | G | 0-0 | SPARE | D05068P | 21 | | | D05598J | 27 | | | 275-276 | |
| 207R | 24 | PL | G | 0-0 | SPARE | D05068P | 39 | | | D05598J | 27 | | | 277-299 | |
| 208B | 24 | PW | IH | 17-6 | 28-41-11 | D04346P | 43 | | | D08614J | 9 | | | 050-099 | |
| 208B | 24 | PW | IH | 18-1 | 28-41-11 | D04346P | 43 | | | D08614J | 9 | | | 150-199, 275-299 | |
| 208R | 24 | PW | IH | 0-0 | 28-41-11 | D04346P | 42 | | | D08614J | 8 | | | ALL | |
| 208Z | | | IH | 0-0 | 28-41-11 | D04346P | 44 | | | D08614J | 7 | | | ALL | |
| 209B | 24 | PW | II | 17-6 | 77-35-11 | D04346P | 23 | | | D08614J | 4 | | | 050-099 | |
| 209B | 24 | PW | II | 18-1 | 77-35-11 | D04346P | 23 | | | D08614J | 4 | | | 150-199, 275-299 | |
| 209R | 24 | PW | II | 0-0 | 77-35-11 | D04346P | 10 | | | D08614J | 5 | | | ALL | |
| 209Z | | | II | 0-0 | 77-35-11 | D04346P | 50 | | | D08614J | 6 | | | ALL | |
| 210B | 24 | PW | IJ | 17-6 | 77-35-11 | D04346P | 46 | | | D08614J | 1 | | | 050-099 | |
| 210B | 24 | PW | IJ | 18-1 | 77-35-11 | D04346P | 46 | | | D08614J | 1 | | | 150-199, 275-299 | |
| 210R | 24 | PW | IJ | 0-0 | 77-35-11 | D04346P | 14 | | | D08614J | 2 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0650

Page 10

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0656 | 286T0656 | | | FUELING, HYDRAULICS, POTABLE WATER FEEDER (continued) | | | | | | | | | | | | |
| 210Z | | | IJ | 0-0 | 77-35-11 | D04346P | | 51 | | | | | D08614J | 3 | | ALL |
| 213B | 22 | PR | IA | 68-1 | 31-31-22 | D08614J | | 11 | | | | | D04770J | 5 | | 050-099 |
| 213B | 22 | PR | K | 78-2 | 31-31-22 | D08614J | | 11 | | | | | D04770J | 5 | | 150-199, 275-299 |
| 213R | 22 | PR | IA | 0-0 | 31-31-22 | D08614J | | 10 | | | | | D04770J | 4 | | 050-099 |
| 213R | 22 | PR | K | 0-0 | 31-31-22 | D08614J | | 10 | | | | | D04770J | 4 | | 150-199, 275-299 |
| 213Z | | | IA | 0-0 | 31-31-22 | D08614J | | 12 | | | | | D04770J | 6 | | 050-099 |
| 213Z | | | K | 0-0 | 31-31-22 | D08614J | | 12 | | | | | D04770J | 6 | | 150-199, 275-299 |
| 214 | 20 | PA | | 68-1 | 31-31-22 | D08614J | | 13 | | | | | D04770J | 7 | | 050-099 |
| 214 | 20 | PA | | 78-2 | 31-31-22 | D08614J | | 13 | | | | | D04770J | 7 | | 150-199, 275-299 |
| 249B | 18 | VG | X | 57-5 | 78-36-21 | D05840P | | REF | DL | | | | D07040J | 8 | | 050-099 |
| 249B | 18 | VG | X | 67-6 | 78-36-21 | D05840P | | REF | DL | | | | D07040J | 8 | | 150-199, 275-278 |
| 249B | 18 | VG | X | 67-6 | 78-36-21 | D07040J | | 8 | | | | | D05840P | REF | DL | 280-299 |
| 249R | 18 | VG | X | 0-0 | 78-36-21 | D05840P | | REF | DL | | | | D07040J | 9 | | 050-099, 150-199, 275-278 |
| 249R | 18 | VG | X | 0-0 | 78-36-21 | D07040J | | 9 | | | | | D05840P | REF | DL | 280-299 |
| 249Z | | | X | 0-0 | 78-36-21 | D05840P | | | | FZ | | | D07040J | =CC | D | 050-099, 150-199, 275-278 |
| 249Z | | | X | 0-0 | 78-36-21 | D07040J | | =CC | D | | | | D05840P | | | FZ 280-299 |
| 250B | 18 | VG | Y | 57-5 | 78-36-21 | D05840P | | CAP | Y | | | | D07040J | 4 | | 050-099 |
| 250B | 18 | VG | Y | 67-6 | 78-36-21 | D05840P | | CAP | Y | | | | D07040J | 4 | | 150-199, 275-278 |
| 250B | 18 | VG | Y | 67-6 | 78-36-21 | D07040J | | 4 | | | | | D05840P | CAP | Y | 280-299 |
| 250R | 18 | VG | Y | 0-0 | 78-36-21 | D05840P | | CAP | Y | | | | D07040J | 5 | | 050-099, 150-199, 275-278 |
| 250R | 18 | VG | Y | 0-0 | 78-36-21 | D07040J | | 5 | | | | | D05840P | CAP | Y | 280-299 |
| 250Z | | | Y | 0-0 | 78-36-21 | D05840P | | DED | | | | | D07040J | =CC | D | 050-099, 150-199, 275-278 |
| 250Z | | | Y | 0-0 | 78-36-21 | D07040J | | =CC | D | | | | D05840P | DED | | 280-299 |
| 251B | 18 | VG | Z | 57-5 | 78-36-21 | D05840P | | CAP | Y | | | | D07040J | 6 | | 050-099 |
| 251B | 18 | VG | Z | 67-6 | 78-36-21 | D05840P | | CAP | Y | | | | D07040J | 6 | | 150-199, 275-278 |
| 251B | 18 | VG | Z | 67-6 | 78-36-21 | D07040J | | 6 | | | | | D05840P | CAP | Y | 280-299 |
| 251R | 18 | VG | Z | 0-0 | 78-36-21 | D05840P | | CAP | Y | | | | D07040J | 7 | | 050-099, 150-199, 275-278 |
| 251R | 18 | VG | Z | 0-0 | 78-36-21 | D07040J | | 7 | | | | | D05840P | CAP | Y | 280-299 |
| 251Z | | | Z | 0-0 | 78-36-21 | D05840P | | DED | | | | | D07040J | =CC | D | 050-099, 150-199, 275-278 |
| 251Z | | | Z | 0-0 | 78-36-21 | D07040J | | =CC | D | | | | D05840P | DED | | 280-299 |
| 252B | 18 | VG | Q | 57-5 | 78-36-21 | D05840P | | REF | DL | | | | D07040J | 10 | | 050-099 |
| 252B | 18 | VG | Q | 67-6 | 78-36-21 | D05840P | | REF | DL | | | | D07040J | 10 | | 150-199, 275-278 |
| 252B | 18 | VG | Q | 67-6 | 78-36-21 | D07040J | | 10 | | | | | D05840P | REF | DL | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0650

Page 11

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|---------|------|---------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0656 | 286T0656 | | | FUELING, HYDRAULICS, POTABLE WATER FEEDER (continued) | | | | | | | | | | | |
| 252R | 18 | VG | Q | 0-0 | 78-36-21 | D05840P | REF | DL | | D07040J | 11 | | | 050-099, 150-199, 275-278 | |
| 252R | 18 | VG | Q | 0-0 | 78-36-21 | D07040J | | | 11 | | | | | 280-299 | |
| 252Z | | | Q | 0-0 | 78-36-21 | D05840P | | | | FZ | D07040J | =CC | DL D | 050-099, 150-199, 275-278 | |
| 252Z | | | Q | 0-0 | 78-36-21 | D07040J | =CC | D | | | | | FZ | 280-299 | |
| 301B | 24 | PX | C | 47-6 | 36-23-21 | D04346P | 30 | | | | D05528J | 33 | | 050-099 | |
| 301B | 24 | PX | C | 58-1 | 36-23-21 | D04346P | 30 | | | | D05528J | 33 | | 150-199, 275-299 | |
| 301R | 24 | PX | C | 0-0 | 36-23-21 | D04346P | 31 | | | | D05528J | 34 | | ALL | |
| 301Y | 24 | PX | C | 0-0 | 36-23-21 | D04346P | 32 | | | | D05528J | 35 | | ALL | |
| 301Z | | | C | 0-0 | 36-23-21 | D04346P | 29 | | | | D05528J | 36 | | ALL | |
| 412R | 22 | PH | | 47-7 | 26-18-22 | D05528J | 52 | | | | D05068P | 18 | | 050-099 | |
| 412R | 22 | PH | | 58-4 | 26-18-22 | D05068P | 18 | | | | D05528J | 52 | | 150-199, 275-299 | |
| 413R | 22 | PH | | 47-7 | 26-18-22 | D05528J | 51 | | | | D05068P | 30 | | 050-099 | |
| 413R | 22 | PH | | 58-4 | 26-18-22 | D05068P | 30 | | | | D05528J | 51 | | 150-199, 275-299 | |
| 502 | 24 | PK | | 13-10 | 78-36-21 | D05840P | 9 | | | | D05068P | 44 | | 050-099 | |
| 502 | 24 | PK | | 13-9 | 78-36-21 | D05840P | 9 | | | | D05068P | 44 | | 150-199, 275-278 | |
| 502 | 24 | PK | | 13-9 | 78-36-21 | D05068P | 44 | | | | D05840P | 9 | | 280-299 | |
| 503 | 24 | PK | | 13-10 | 78-36-21 | D05840P | 11 | | | | D05068P | 45 | | 050-099 | |
| 503 | 24 | PK | | 13-9 | 78-36-21 | D05840P | 11 | | | | D05068P | 45 | | 150-199, 275-278 | |
| 503 | 24 | PK | | 13-9 | 78-36-21 | D05068P | 45 | | | | D05840P | 11 | | 280-299 | |
| 504 | 24 | PK | | 13-10 | 78-36-21 | D05840P | 10 | | | | D05068P | 46 | | 050-099 | |
| 504 | 24 | PK | | 13-9 | 78-36-21 | D05840P | 10 | | | | D05068P | 46 | | 150-199, 275-278 | |
| 504 | 24 | PK | | 13-9 | 78-36-21 | D05068P | 46 | | | | D05840P | 10 | | 280-299 | |
| 505 | 24 | PK | | 13-10 | 78-36-21 | D05840P | 12 | | | | D05068P | 47 | | 050-099 | |
| 505 | 24 | PK | | 13-9 | 78-36-21 | D05840P | 12 | | | | D05068P | 47 | | 150-199, 275-278 | |
| 505 | 24 | PK | | 13-9 | 78-36-21 | D05068P | 47 | | | | D05840P | 12 | | 280-299 | |
| 506 | 24 | PK | | 13-10 | 78-36-21 | D05840P | 17 | | | | D05068P | 48 | | 050-099 | |
| 506 | 24 | PK | | 13-9 | 78-36-21 | D05840P | 17 | | | | D05068P | 48 | | 150-199, 275-278 | |
| 506 | 24 | PK | | 13-9 | 78-36-21 | D05068P | 48 | | | | D05840P | 17 | | 280-299 | |
| 507 | 24 | PK | | 13-10 | 78-36-21 | D05840P | 18 | | | | D05068P | 49 | | 050-099 | |
| 507 | 24 | PK | | 13-9 | 78-36-21 | D05840P | 18 | | | | D05068P | 49 | | 150-199, 275-278 | |
| 507 | 24 | PK | | 13-9 | 78-36-21 | D05068P | 49 | | | | D05840P | 18 | | 280-299 | |
| 508 | 22 | PA | | 13-10 | 78-36-21 | D05068P | 50 | | | | D05840P | 24 | | 050-099 | |
| 508 | 22 | PA | | 13-9 | 78-36-21 | D05068P | 50 | | | | D05840P | 24 | | 150-166, 275-276, 280-299 | |
| 508 | 22 | PA | | 13-9 | 78-36-21 | D05840P | 24 | | | | D05068P | 50 | | 167-199, 277-278 | |
| 509 | 24 | PK | | 13-10 | 78-36-21 | D05068P | 51 | | | | D05840P | 23 | | 050-099 | |

WIRE LIST
D280T132

91-21-11
Section W0650
Page 12
Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0656 | 286T0656 | | | FUELING, HYDRAULICS, POTABLE WATER FEEDER (continued) | | | | | | | | | | | | |
| 509 | 24 | | PK | 13-9 | 78-36-21 | D05068P | 51 | | | | D05840P | 23 | | | 150-166, 275-276, 280-299 | |
| 509 | 24 | | PK | 13-9 | 78-36-21 | D05840P | 23 | | | | D05068P | 51 | | | 167-199, 277-278 | |
| 801 | 22 | | PA | 20-7 | 78-36-21 | D05068P | 54 | | | | D07162J | 1 | | | 050-099 | |
| 801 | 22 | | PA | 24-0 | 78-36-21 | D05068P | 54 | | | | D07162J | 1 | | | 150-199, 275-299 | |
| 802 | 22 | | PA | 20-7 | 78-36-21 | D05068P | 55 | | | | D07162J | 2 | | | 050-099 | |
| 802 | 22 | | PA | 24-0 | 78-36-21 | D05068P | 55 | | | | D07162J | 2 | | | 150-199, 275-299 | |
| 803 | 22 | | PA | 20-7 | 78-36-21 | D05068P | 58 | | | | D07162J | 3 | | | 050-099 | |
| 803 | 22 | | PA | 24-0 | 78-36-21 | D05068P | 58 | | | | D07162J | 3 | | | 150-199, 275-299 | |
| 804 | 22 | | PA | 20-7 | 78-36-21 | D05068P | 57 | | | | D07162J | 4 | | | 050-099 | |
| 804 | 22 | | PA | 24-0 | 78-36-21 | D05068P | 57 | | | | D07162J | 4 | | | 150-199, 275-299 | |
| 805 | 22 | | PA | 20-7 | 78-36-21 | D05068P | 56 | | | | D07162J | 5 | | | 050-099 | |
| 805 | 22 | | PA | 24-0 | 78-36-21 | D05068P | 56 | | | | D07162J | 5 | | | 150-199, 275-299 | |
| 806 | 22 | | PA | 30-2 | 78-36-21 | D05840P | 19 | | | | D07162J | 6 | | | 050-099 | |
| 806 | 22 | | PA | 35-0 | 78-36-21 | D05840P | 19 | | | | D07162J | 6 | | | 150-199, 275-299 | |
| 807 | 22 | | PA | 20-7 | 78-36-21 | D05068P | 60 | | | | D07162J | 7 | | | 050-099 | |
| 807 | 22 | | PA | 24-0 | 78-36-21 | D05068P | 60 | | | | D07162J | 7 | | | 150-199, 275-299 | |
| 808 | 22 | | PA | 30-2 | 78-36-21 | D05840P | 21 | | | | D07162J | 8 | | | 050-099 | |
| 808 | 22 | | PA | 35-0 | 78-36-21 | D05840P | 21 | | | | D07162J | 8 | | | 150-199, 275-299 | |
| 809 | 22 | | PA | 30-2 | 78-36-21 | D05840P | 22 | | | | D07162J | 9 | | | 050-099 | |
| 809 | 22 | | PA | 35-0 | 78-36-21 | D05840P | 22 | | | | D07162J | 9 | | | 150-199, 275-299 | |
| FRA | | | | 0-0 | 29-33-11 | D05528J | | | | FA | D05528J | 28 | | | ALL | |
| FRB | | | | 0-0 | 29-33-11 | D05528J | | | | FA | D05528J | 29 | | | ALL | |
| FRC | | | | 0-0 | 29-33-11 | D05528J | | | | FA | D05528J | 48 | | | ALL | |
| FRD | | | | 0-0 | 29-33-11 | D04916J | | | | FB | D04916J | 4 | | | ALL | |
| FRE | | | | 0-0 | 29-33-11 | D04916J | | | | FB | D04916J | 5 | | | ALL | |
| FRF | | | | 0-0 | 29-33-11 | D04916J | | | | FB | D04916J | 14 | | | ALL | |
| W0657 | 286T0657 | | | CONTRAHELICAL CABLE-FIRST OFFICER AUDIO SELECT PANEL | | | | | | | | | | | | |
| 0BBK | 24 | | P7 A | 26-0 | 23-51-21 | D00255 | 30 | | | | D04603J | 30 | | | ALL | |
| 0BBN | 24 | | P7 A | 0-0 | 23-51-21 | D00255 | 33 | | | | D04603J | 33 | | | ALL | |
| 0BGK | 24 | | P7 A | 0-0 | 23-51-21 | D00255 | 34 | | | | D04603J | 34 | | | ALL | |
| 0BLG | 24 | | P7 A | 0-0 | 23-51-21 | D00255 | 29 | | | | D04603J | 29 | | | ALL | |
| 0BLK | 24 | | P7 A | 0-0 | 23-51-21 | D00255 | 5 | | | | D04603J | 5 | | | ALL | |
| 0BLU | 24 | | P7 A | 0-0 | 23-51-21 | D00255 | 2 | | | | D04603J | 2 | | | ALL | |
| 0BLY | 24 | | P7 A | 0-0 | 23-51-21 | D00255 | 28 | | | | D04603J | 28 | | | ALL | |
| 0BOR | 24 | | P7 A | 0-0 | 23-51-21 | D00255 | 32 | | | | D04603J | 32 | | | ALL | |
| 0BPR | 24 | | P7 A | 0-0 | 23-51-21 | D00255 | 31 | | | | D04603J | 31 | | | ALL | |
| 0BRN | 24 | | P7 A | 0-0 | 23-51-21 | D00255 | 8 | | | | D04603J | 8 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0650

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0657 | 286T0657 | | | CONTRAHELICAL CABLE-FIRST OFFICER AUDIO SELECT PANEL (continued) | | | | | | | | | | | |
| 0GRN | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 4 | | D04603J | | 4 | | ALL |
| 0ORG | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 7 | | D04603J | | 7 | | ALL |
| 0PNK | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 9 | | D04603J | | 9 | | ALL |
| 0PUR | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 6 | | D04603J | | 6 | | ALL |
| 0RBK | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 23 | | D04603J | | 23 | | ALL |
| 0RBR | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 26 | | D04603J | | 26 | | ALL |
| 0RGR | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 22 | | D04603J | | 22 | | ALL |
| 0ROR | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 25 | | D04603J | | 25 | | ALL |
| 0RPR | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 24 | | D04603J | | 24 | | ALL |
| 0RYG | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 27 | | D04603J | | 27 | | ALL |
| 0RYL | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 21 | | D04603J | | 21 | | ALL |
| 0UNI | 20 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 20 | | D04603J | | 20 | | ALL |
| 0WBK | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 15 | | D04603J | | 15 | | ALL |
| 0WBN | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 18 | | D04603J | | 18 | | ALL |
| 0WBU | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 12 | | D04603J | | 12 | | ALL |
| 0WBY | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 19 | | D04603J | | 19 | | ALL |
| 0WGR | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 14 | | D04603J | | 14 | | ALL |
| 0WHT | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 10 | | D04603J | | 10 | | ALL |
| 0WOR | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 17 | | D04603J | | 17 | | ALL |
| 0WPR | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 16 | | D04603J | | 16 | | ALL |
| 0WRB | 20 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 1 | | D04603J | | 1 | | ALL |
| 0WRD | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 11 | | D04603J | | 11 | | ALL |
| 0WYL | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 13 | | D04603J | | 13 | | ALL |
| 0YBK | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 36 | | D04603J | | 36 | | ALL |
| 0YEL | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 3 | | D04603J | | 3 | | ALL |
| 0YGR | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 35 | | D04603J | | 35 | | ALL |
| 0YOR | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 38 | | D04603J | | 38 | | ALL |
| 0YPR | 24 | | P7 | A | 0-0 | 23-51-21 | D00255 | | 37 | | D04603J | | 37 | | ALL |
| W0658 | 286T0658 | | | RAT. CONT & INDICATION HYD SYS C | | | | | | | | | | | |
| 002 | 20 | | UA | | 88-8 | 29-21-31 | D04958P | | 2 | | K00234 | X1 | N | | 050-099 |
| 002 | 20 | | UA | | 98-9 | 29-21-31 | D04958P | | 2 | | K00234 | X1 | N | | 150-199, 275-299 |
| 003 | 20 | | UA | | 89-3 | 29-21-31 | D04958P | | 3 | | K00235 | X1 | N | | 050-099 |
| 003 | 20 | | UA | | 99-3 | 29-21-31 | D04958P | | 3 | | K00235 | X1 | N | | 150-199, 275-299 |
| 005 | 20 | | UA | | 89-4 | 29-21-31 | D04958P | | 5 | | K00236 | X1 | N | | 050-099 |
| 005 | 20 | | UA | | 99-5 | 29-21-31 | D04958P | | 5 | | K00236 | X1 | N | | 150-199, 275-299 |
| 006 | 20 | | UA | | 71-10 | 29-21-31 | D04958P | | 6 | | D04316J | | 6 | | 050-099 |
| 006 | 20 | | UA | | 81-9 | 29-21-31 | D04958P | | 6 | | D04316J | | 6 | | 150-199, 275-299 |
| 007 | 20 | | UA | | 88-6 | 29-21-31 | D04958P | | 7 | | SM00001 | | 9 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0650
Page 14
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|--------|------|------|--------|-------|------|------|---------|-------------|----|--|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0658 | 286T0658 | | | RAT. CONT & INDICATION HYD SYS C (continued) | | | | | | | | | | | | | | | |
| 007 | 20 | | UA | 98-5 | 29-21-31 | D04958P | | 7 | | | | | | SM00001 | | 9 | | | 150-199, 275-299 |
| 008 | 18 | | UA | 4-10 | 29-21-31 | K00235 | | | X2 | N | | | | SP01552 | | 9 | | | ALL |
| 009 | 18 | | UA | 5-1 | 29-21-31 | SP01554 | | | | 9 | | | | GD00028 | D.. | 2 | | | 050-099 |
| 009 | 18 | | UA | 4-8 | 29-21-31 | SP01554 | | | | 9 | | | | GD00028 | D.. | 2 | | | 150-199, 275-299 |
| 010 | 18 | | UA | 4-0 | 29-21-31 | SP01556 | | | | 9 | | | | GD00028 | D.. | 2 | | | 050-099 |
| 010 | 18 | | UA | 3-7 | 29-21-31 | SP01556 | | | | 9 | | | | GD00028 | D.. | 2 | | | 150-199, 275-299 |
| 011 | 18 | | UA | 4-9 | 29-21-31 | SM00001 | | | | 9 | | | | D02354 | | 5 | | | 050-099 |
| 011 | 18 | | UA | 4-7 | 29-21-31 | SM00001 | | | | 9 | | | | D02354 | | 5 | | | 150-199, 275-299 |
| 015 | 18 | | UA | 22-7 | 29-21-31 | D04316J | | | | 5 | | | | K00234 | X2 | N | | | 050-099 |
| 015 | 18 | | UA | 22-11 | 29-21-31 | D04316J | | | | 5 | | | | K00234 | X2 | N | | | 150-199, 275-299 |
| 016 | 18 | | UA | 5-1 | 29-21-31 | SP01560 | | | | 9 | | | | GD00028 | D.. | 2 | | | 050-099 |
| 016 | 18 | | UA | 4-8 | 29-21-31 | SP01560 | | | | 9 | | | | GD00028 | D.. | 2 | | | 150-199, 275-299 |
| 017 | 20 | | UA | 4-11 | 29-21-31 | D04316J | | | | 7 | | | | GD02620 | D.. | 2 | | | 050-099 |
| 017 | 20 | | UA | 5-0 | 29-21-31 | D04316J | | | | 7 | | | | GD02620 | D.. | 2 | | | 150-199, 275-299 |
| 018 | 20 | | UA | 4-11 | 29-11-32 | GD02620 | | | D.. | 2 | | | | D04316J | | 8 | | | 050-099 |
| 018 | 20 | | UA | 5-0 | 29-11-32 | GD02620 | | | D.. | 2 | | | | D04316J | | 8 | | | 150-199, 275-299 |
| 019 | 20 | | UA | 71-10 | 29-11-32 | D04958P | | | | 9 | | | | D04316J | | 9 | | | 050-099 |
| 019 | 20 | | UA | 81-9 | 29-11-32 | D04958P | | | | 9 | | | | D04316J | | 9 | | | 150-199, 275-299 |
| 022 | 16 | | UA | 48-11 | 25-65-12 | SP02566 | | | | S | | | | D01128 | A | FM | | | 050-099 |
| 022 | 16 | | UA | 49-5 | 25-65-12 | SP02566 | | | | S | | | | D01128 | A | FM | | | 150-199, 275-299 |
| 024 | 16 | | UA | 7-8 | 25-65-12 | GD00028 | | | D.. | 2 | | | | D01128 | B | FM | | | ALL |
| 028 | 18 | | UA | 4-9 | 29-21-31 | D02354 | | | | 6 | | | | SM00001 | | 9 | | | 050-099 |
| 028 | 18 | | UA | 4-7 | 29-21-31 | D02354 | | | | 6 | | | | SM00001 | | 9 | | | 150-199, 275-299 |
| 029 | 18 | | UA | 9-1 | 29-21-31 | D02354 | | | | 4 | | | | GD00028 | S.. | 2 | | | 050-099 |
| 029 | 18 | | UA | 8-9 | 29-21-31 | D02354 | | | | 4 | | | | GD00028 | S.. | 2 | | | 150-199, 275-299 |
| 030 | 18 | | UA | 4-11 | 29-21-31 | SP01562 | | | | 9 | | | | K00236 | X2 | N | | | 050-099 |
| 030 | 18 | | UA | 5-0 | 29-21-31 | SP01562 | | | | 9 | | | | K00236 | X2 | N | | | 150-199, 275-299 |
| 031 | 18 | | UA | 2-2 | 29-21-31 | SM00001 | | | | 9 | | | | SP01558 | | 9 | | | 050-099 |
| 031 | 18 | | UA | 2-4 | 29-21-31 | SM00001 | | | | 9 | | | | SP01558 | | 9 | | | 150-199, 275-299 |
| 032 | 18 | | UA | 26-7 | 29-21-31 | D04316J | | | | 2 | | | | D02354 | | 7 | | | 050-099 |
| 032 | 18 | | UA | 26-8 | 29-21-31 | D04316J | | | | 2 | | | | D02354 | | 7 | | | 150-199, 275-299 |
| 033 | 18 | | UA | 4-11 | 29-21-31 | D04316J | | | | 11 | | | | GD02620 | D.. | 2 | | | 050-099 |
| 033 | 18 | | UA | 5-0 | 29-21-31 | D04316J | | | | 11 | | | | GD02620 | D.. | 2 | | | 150-199, 275-299 |
| 201B | 20 | | VG | A | 26-7 | 29-21-31 | D02354 | | | 2 | | | | D04316J | | 4 | | | 050-099 |
| 201B | 20 | | VG | A | 26-8 | 29-21-31 | D02354 | | | 2 | | | | D04316J | | 4 | | | 150-199, 275-299 |
| 201R | 20 | | VG | A | 0-0 | 29-21-31 | D02354 | | | 1 | | | | D04316J | | 3 | | | ALL |
| 201Z | | | | A | 0-0 | 29-21-31 | D02354 | | | 3 | | | | D04316J | | 1 | | | ALL |
| 501 | 20 | | UA | 71-10 | SPARE | D04958P | | | | 10 | | | | D04316J | | 10 | | | 050-099 |
| 501 | 20 | | UA | 81-9 | SPARE | D04958P | | | | 10 | | | | D04316J | | 10 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0650

Page 15

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0658 | 286T0658 | | | RAT. CONT & INDICATION HYD SYS C (continued) | | | | | | | | | | | |
| A-A | | | | 0-0 | 29-21-31 | S00365 | | 1 | | SP01554 | | 9 | | ALL | |
| A-B | | | | 0-0 | 29-21-31 | S00365 | | 3 | | S00365 | CAP | Y | | ALL | |
| A-C | | | | 0-0 | 29-21-31 | S00365 | | 2 | | SP01552 | | 9 | | ALL | |
| A-D | | | | 0-0 | 29-21-31 | S00365 | | 6 | | S00365 | CAP | Y | | ALL | |
| A-E | | | | 0-0 | 29-21-31 | S00365 | | 5 | | S00365 | CAP | Y | | ALL | |
| A-F | | | | 0-0 | 29-21-31 | S00365 | | 4 | | S00365 | CAP | Y | | ALL | |
| B-A | | | | 0-0 | 29-21-31 | S00369 | | 1 | | SP01556 | | 9 | | ALL | |
| B-B | | | | 0-0 | 29-21-31 | S00369 | | 3 | | S00369 | CAP | Y | | ALL | |
| B-C | | | | 0-0 | 29-21-31 | S00369 | | 2 | | SP01558 | | 9 | | ALL | |
| B-D | | | | 0-0 | 29-21-31 | S00369 | | 6 | | S00369 | CAP | Y | | ALL | |
| B-E | | | | 0-0 | 29-21-31 | S00369 | | 5 | | S00369 | CAP | Y | | ALL | |
| B-F | | | | 0-0 | 29-21-31 | S00369 | | 4 | | S00369 | CAP | Y | | ALL | |
| C-A | | | | 0-0 | 29-21-31 | S00501 | | 1 | | SP01560 | | 9 | | ALL | |
| C-B | | | | 0-0 | 29-21-31 | S00501 | | 3 | | S00501 | CAP | Y | | ALL | |
| C-C | | | | 0-0 | 29-21-31 | S00501 | | 2 | | SP01562 | | 9 | | ALL | |
| C-D | | | | 0-0 | 29-21-31 | S00501 | | 5 | | S00501 | CAP | Y | | ALL | |
| C-E | | | | 0-0 | 29-21-31 | S00501 | | 6 | | S00501 | CAP | Y | | ALL | |
| C-F | | | | 0-0 | 29-21-31 | S00501 | | 4 | | S00501 | CAP | Y | | ALL | |
| W0659 | 286T0659 | | | CONTRAHELICAL CABLE-FIRST OBSERVER AUDIO SELECT PANEL | | | | | | | | | | | |
| 0BBK | 24 | P7 | A | 27-0 | 23-51-41 | D00549 | | 30 | | D04607J | | 30 | | ALL | |
| 0BBN | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 33 | | D04607J | | 33 | | ALL | |
| 0BGK | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 34 | | D04607J | | 34 | | ALL | |
| 0BLG | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 29 | | D04607J | | 29 | | ALL | |
| 0BLK | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 5 | | D04607J | | 5 | | ALL | |
| 0BLU | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 2 | | D04607J | | 2 | | ALL | |
| 0BLY | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 28 | | D04607J | | 28 | | ALL | |
| 0BOR | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 32 | | D04607J | | 32 | | ALL | |
| 0BPR | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 31 | | D04607J | | 31 | | ALL | |
| 0BRN | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 8 | | D04607J | | 8 | | ALL | |
| 0GRN | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 4 | | D04607J | | 4 | | ALL | |
| 0ORG | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 7 | | D04607J | | 7 | | ALL | |
| 0PNK | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 9 | | D04607J | | 9 | | ALL | |
| 0PUR | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 6 | | D04607J | | 6 | | ALL | |
| 0RBK | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 23 | | D04607J | | 23 | | ALL | |
| 0RBR | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 26 | | D04607J | | 26 | | ALL | |
| 0RGR | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 22 | | D04607J | | 22 | | ALL | |
| 0ROR | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 25 | | D04607J | | 25 | | ALL | |
| 0RPR | 24 | P7 | A | 0-0 | 23-51-41 | D00549 | | 24 | | D04607J | | 24 | | ALL | |

WIRE LIST

D280T132

91-21-11
 Section W0650
 Page 16
 Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0659 | 286T0659 | | | CONTRAHELICAL CABLE-FIRST OBSERVER AUDIO SELECT PANEL (continued) | | | | | | | | | | | |
| 0RYG | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 27 | | | D04607J | | 27 | | ALL |
| 0RYL | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 21 | | | D04607J | | 21 | | ALL |
| 0UNI | 20 | | P7 A | 0-0 | 23-51-41 | D00549 | | 20 | | | D04607J | | 20 | | ALL |
| 0WBK | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 15 | | | D04607J | | 15 | | ALL |
| 0WBN | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 18 | | | D04607J | | 18 | | ALL |
| 0WBU | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 12 | | | D04607J | | 12 | | ALL |
| 0WBY | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 19 | | | D04607J | | 19 | | ALL |
| 0WGR | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 14 | | | D04607J | | 14 | | ALL |
| 0WHT | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 10 | | | D04607J | | 10 | | ALL |
| 0WOR | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 17 | | | D04607J | | 17 | | ALL |
| 0WPR | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 16 | | | D04607J | | 16 | | ALL |
| 0WRB | 20 | | P7 A | 0-0 | 23-51-41 | D00549 | | 1 | | | D04607J | | 1 | | ALL |
| 0WRD | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 11 | | | D04607J | | 11 | | ALL |
| 0WYL | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 13 | | | D04607J | | 13 | | ALL |
| 0YBK | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 36 | | | D04607J | | 36 | | ALL |
| 0YEL | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 3 | | | D04607J | | 3 | | ALL |
| 0YGR | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 35 | | | D04607J | | 35 | | ALL |
| 0YOR | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 38 | | | D04607J | | 38 | | ALL |
| 0YPR | 24 | | P7 A | 0-0 | 23-51-41 | D00549 | | 37 | | | D04607J | | 37 | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|----------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0660 | 286T0660 | | | FWD CARGO DOOR AND LIGHTS | | | | | | | | | | | | |
| 005 | 20 | PA | | | 5-0 | 52-34-11 | D04306J | 14 | | | | GD04594 | S.. | E | | 050-099 |
| 005 | 20 | PA | | | 4-0 | 52-34-11 | D04306J | 14 | | | | GD04594 | S.. | E | | 150-199, 275-299 |
| 007 | 20 | PA | | | 4-0 | 33-31-61 | L00137 | | GND | E | | GD03856 | S.. | E | | 050-099 |
| 009 | 20 | PA | | | 17-0 | 33-31-61 | D04304P | 22 | | | | D04306J | 22 | | | 050-099 |
| 009 | 20 | PA | | | 17-0 | 33-31-61 | D04306J | 22 | | | | D04304P | 22 | | | 150-199, 275-299 |
| 010 | 20 | PA | | | 16-0 | 33-31-61 | D04306J | 23 | | | | GD04324 | A.. | 2 | | ALL |
| 011 | 20 | PA | | | 17-0 | 52-34-11 | D04304P | 11 | | | | D04306J | 11 | | | ALL |
| 012 | 20 | PA | | | 17-0 | 52-34-11 | D04304P | 12 | | | | D04306J | 12 | | | ALL |
| 013 | 20 | PA | | | 17-0 | 52-34-11 | D04304P | 13 | | | | D04306J | 13 | | | ALL |
| 014 | 20 | PA | | | 17-0 | 52-34-11 | D04304P | 14 | | | | D04306J | 15 | | | ALL |
| 015 | 20 | PA | | | 17-0 | 52-34-11 | D04304P | 24 | | | | D04306J | 24 | | | ALL |
| 016 | 20 | PA | | | 17-0 | 52-34-11 | D04304P | 16 | | | | D04306J | 16 | | | ALL |
| 017 | 20 | PA | | | 17-0 | 33-31-61 | D04304P | 17 | | | | D04306J | 17 | | | 050-099 |
| 017 | 20 | PA | | | 17-0 | 33-31-61 | D04306J | 17 | | | | D04304P | 17 | | | 150-199, 275-299 |
| 018 | 20 | PA | | | 40-0 | 33-31-61 | D04304P | 18 | | | | L00137 | 28V | E | | 050-099 |
| 018 | 20 | PA | | | 41-0 | 33-31-61 | D04304P | 18 | | | | L00137 | 28V | E | | 150-199, 275-299 |
| 019 | 18 | PA | | | 1-0 | 33-37-11 | D04304P | 19 | | | | SM00001 | | 9 | | 050-099 |
| 019 | 16 | PA | | | 1-0 | 33-37-11 | D04304P | 19 | | | | SM00001 | | 9 | | 150-199, 275-299 |
| 020 | 20 | PA | | | 17-0 | 33-37-11 | D04304P | 20 | | | | D04306J | 20 | | | 050-099 |
| 020 | 18 | PA | | | 17-0 | 33-37-11 | D04304P | 15 | | | | D04306J | 20 | DK | | 150-199, 275-299 |
| 023 | 18 | PA | | | 1-0 | 33-37-11 | D04304P | 23 | | | | SM00002 | | 9 | | 050-099 |
| 023 | 16 | PA | | | 1-0 | 33-37-11 | D04304P | 23 | | | | SM00002 | | 9 | | 150-199, 275-299 |
| 033 | 18 | PA | | | 15-0 | 33-37-11 | L00161 | | =P | C | * | SM00001 | | 9 | | 050-099 |
| 033 | 16 | PA | | | 16-0 | 33-37-11 | L00161 | | =P | C | * | SM00001 | | 9 | | 150-199, 275-299 |
| 034 | 18 | PA | | | 2-0 | 33-37-11 | L00161 | | =G | C | | GD00524 | A.. | E | | 050-099 |
| 034 | 16 | PA | | | 2-0 | 33-37-11 | L00161 | | =G | C | | GD00524 | A.. | E | | 150-199, 275-299 |
| 035 | 18 | PA | | | 9-0 | 33-37-11 | L00161 | | =P | C | * | L00162 | =P | C | | 050-099 |
| 035 | 16 | PA | | | 9-0 | 33-37-11 | L00161 | | =P | C | * | L00162 | =P | C | | 150-199, 275-299 |
| 036 | 18 | PA | | | 2-0 | 33-37-11 | L00162 | | =G | C | | GD00526 | A.. | E | | 050-099 |
| 036 | 16 | PA | | | 2-0 | 33-37-11 | L00162 | | =G | C | | GD00526 | A.. | E | | 150-199, 275-299 |
| 037 | 18 | PA | | | 17-0 | 33-37-11 | L00163 | | =P | C | * | SM00002 | | 9 | | 050-099 |
| 037 | 16 | PA | | | 18-0 | 33-37-11 | L00163 | | =P | C | * | SM00002 | | 9 | | 150-199, 275-299 |
| 038 | 18 | PA | | | 2-0 | 33-37-11 | L00163 | | =G | C | | GD00528 | A.. | E | | 050-099 |
| 038 | 16 | PA | | | 2-0 | 33-37-11 | L00163 | | =G | C | | GD00528 | A.. | E | | 150-199, 275-299 |
| 039 | 18 | PA | | | 9-0 | 33-37-11 | L00163 | | =P | C | * | L00164 | =P | C | | 050-099 |
| 039 | 16 | PA | | | 9-0 | 33-37-11 | L00163 | | =P | C | * | L00164 | =P | C | | 150-199, 275-299 |
| 040 | 18 | PA | | | 2-0 | 33-37-11 | L00164 | | =G | C | | GD00530 | A.. | E | | 050-099 |
| 040 | 16 | PA | | | 2-0 | 33-37-11 | L00164 | | =G | C | | GD00530 | A.. | E | | 150-199, 275-299 |
| 041 | 18 | PA | | | 24-0 | 33-37-11 | L00165 | | =P | C | | SM00002 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0660 | 286T0660 | | | FWD CARGO DOOR AND LIGHTS (continued) | | | | | | | | | | | | | |
| 042 | 18 | | PA | 2-0 | 33-37-11 | L00165 | =G | C | | | | | GD00532 | A.. | E | | 050-099 |
| 042 | 16 | | PA | 2-0 | 33-37-11 | L00165 | =G | C | | | | | GD00532 | A.. | E | | 150-199, 275-299 |
| 043 | 18 | | PA | 30-0 | 33-37-11 | SM00001 | | 9 | | | | | L00166 | =P | C | * | 050-099 |
| 043 | 16 | | PA | 30-0 | 33-37-11 | SM00001 | | 9 | | | | | L00166 | =P | C | | 150-199, 275-299 |
| 044 | 18 | | PA | 2-0 | 33-37-11 | L00166 | =G | C | | | | | GD00534 | A.. | E | | 050-099 |
| 044 | 16 | | PA | 2-0 | 33-37-11 | L00166 | =G | C | | | | | GD00534 | A.. | E | | 150-199, 275-299 |
| 045 | 18 | | PA | 29-0 | 33-37-11 | L00167 | =P | C | | | * | | SM00002 | | 9 | | 050-099 |
| 045 | 16 | | PA | 30-0 | 33-37-11 | L00167 | =P | C | | | * | | SM00002 | | 9 | | 150-199, 275-299 |
| 046 | 18 | | PA | 2-0 | 33-37-11 | L00167 | =G | C | | | | | GD00536 | A.. | E | | 050-099 |
| 046 | 16 | | PA | 2-0 | 33-37-11 | L00167 | =G | C | | | | | GD00536 | A.. | E | | 150-199, 275-299 |
| 047 | 18 | | PA | 9-0 | 33-37-11 | L00167 | =P | C | | | * | | L00168 | =P | C | | 050-099 |
| 047 | 16 | | PA | 9-0 | 33-37-11 | L00167 | =P | C | | | * | | L00168 | =P | C | | 150-199, 275-299 |
| 048 | 18 | | PA | 2-0 | 33-37-11 | L00168 | =G | C | | | | | GD00538 | A.. | E | | 050-099 |
| 048 | 16 | | PA | 2-0 | 33-37-11 | L00168 | =G | C | | | | | GD00538 | A.. | E | | 150-199, 275-299 |
| 049 | 18 | | PA | 9-0 | 33-37-11 | L00169 | =P | C | | | | | L00170 | =P | C | * | 050-099 |
| 049 | 16 | | PA | 9-0 | 33-37-11 | L00169 | =P | C | | | * | | L00170 | =P | C | | 150-199, 275-299 |
| 050 | 18 | | PA | 2-0 | 33-37-11 | L00169 | =G | C | | | | | GD00540 | A.. | E | | 050-099 |
| 050 | 16 | | PA | 2-0 | 33-37-11 | L00169 | =G | C | | | | | GD00540 | A.. | E | | 150-199, 275-299 |
| 051 | 18 | | PA | 30-0 | 33-37-11 | L00170 | =P | C | | | * | | L00166 | =P | C | * | 050-099 |
| 052 | 18 | | PA | 2-0 | 33-37-11 | L00170 | =G | C | | | | | GD00542 | A.. | E | | 050-099 |
| 052 | 16 | | PA | 2-0 | 33-37-11 | L00170 | =G | C | | | | | GD00542 | A.. | E | | 150-199, 275-299 |
| 053 | 16 | | PA | 25-0 | 33-37-11 | L00165 | =P | C | | | | | SM00002 | | 9 | | 150-199, 275-299 |
| 054 | 16 | | PA | 2-0 | 33-37-11 | SM00001 | | 9 | | | | | SM00004 | | 9 | | 150-199, 275-299 |
| 055 | 16 | | PA | 14-0 | 33-37-11 | L00827 | =P | C | | | | | L00167 | =P | C | * | 150-199, 275-299 |
| 056 | 16 | | PA | 44-0 | 33-37-11 | SM00004 | | 9 | | | | | L00828 | =P | C | | 150-199, 275-299 |
| 057 | 16 | | PA | 2-0 | 33-37-11 | L00827 | =G | C | | | | | GD04860 | A.. | E | | 150-199, 275-299 |
| 058 | 16 | | PA | 2-0 | 33-37-11 | L00828 | =G | C | | | | | GD04862 | A.. | E | | 150-199, 275-299 |
| 059 | 16 | | PA | 46-0 | 33-37-11 | L00169 | =P | C | | | * | | SM00004 | | 9 | | 150-199, 275-299 |
| 063 | 20 | | PA | 16-0 | 33-31-61 | D04306J | | 18 | | | | | GD04324 | A.. | 2 | | ALL |
| 064 | 20 | | PA | 16-0 | 33-37-11 | D04306J | | 21 | | | | | GD04324 | A.. | 2 | | 050-099 |
| 064 | 18 | | PA | 16-0 | 33-37-11 | D04306J | | 21 | DK | | | | GD04324 | A.. | 2 | | 150-199, 275-299 |
| 065 | 20 | | PA | 4-0 | 33-31-61 | L00137 | | RTN | E | | | | GD00476 | A.. | E | | 050-099, 155-199, 277-299 |
| 065 | 20 | | PA | 4-0 | 33-31-61 | L00137 | GND | E | | | | | GD00476 | A.. | E | | 150-154, 275-276 |
| 077 | 20 | | PA | 4-0 | 33-31-61 | L00137 | CGND | E | | | | | GD03856 | S.. | E | | 150-154, 275-276 |
| 077 | 20 | | PA | 4-0 | 33-31-61 | L00137 | GND | E | | | | | GD03856 | S.. | E | | 155-199, 277-299 |
| 202B | 24 | | PL | B | 17-0 | 52-34-13 | | 3 | | | | | D04306J | | 3 | | ALL |
| 202R | 24 | | PL | B | 0-0 | 52-34-13 | | 4 | | | | | D04306J | | 4 | | ALL |
| 203B | 24 | | PL | C | 17-0 | 52-34-13 | | 5 | | | | | D04306J | | 5 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0660 | 286T0660 | | | FWD CARGO DOOR AND LIGHTS (continued) | | | | | | | | | | | |
| 203R | 24 | PL | C | | 0-0 | 52-34-13 | D04304P | | | | D04306J | 6 | | | ALL |
| 204B | 24 | PL | D | | 17-0 | 52-71-13 | D04304P | | | | D04306J | 7 | | | ALL |
| 204R | 24 | PL | D | | 0-0 | 52-71-13 | D04304P | | | | D04306J | 8 | | | ALL |
| 205B | 24 | PL | E | | 17-0 | 52-34-13 | D04304P | | | | D04306J | 9 | | | ALL |
| 205R | 24 | PL | E | | 0-0 | 52-34-13 | D04304P | | | 10 | D04306J | | | | ALL |
| 206B | 24 | PL | F | | 17-0 | 52-71-13 | D04304P | | | | D04306J | 1 | | | ALL |
| 206R | 24 | PL | F | | 0-0 | 52-71-13 | D04304P | | | 2 | D04306J | | | | ALL |
| W0662 | 286T0662 | | | AFT CARGO DOOR AND LIGHTS | | | | | | | | | | | |
| 005 | 20 | PA | | | 11-7 | 52-35-11 | D04314P | | | 14 | GD00456 | S.. | E | | 050-099 |
| 005 | 20 | PA | | | 8-7 | 52-35-11 | D04314P | | | 14 | GD00456 | S.. | E | | 150-199, 275-299 |
| 006 | 20 | PA | | | 5-5 | 52-35-11 | D01998 | | | 5 | GD03662 | S.. | E | | 050-099 |
| 006 | 20 | PA | | | 2-9 | 52-35-11 | D01998 | | | 5 | GD03662 | S.. | E | | 150-199, 275-299 |
| 007 | 20 | PA | | | 5-4 | 33-31-61 | L00139 | CGND | E | | GD00408 | S.. | 2 | | 050-099, 150-199 |
| 008 | 20 | PA | | | 1-10 | 33-31-61 | L00140 | CGND | E | | GD03852 | S.. | E | | 050-099, 150-199 |
| 009 | 20 | PA | | | 2-3 | 33-31-61 | L00138 | GND | E | | GD03854 | S.. | E | | 050-099, 155-199, 277-299 |
| 009 | 20 | PA | | | 2-3 | 33-31-61 | L00138 | CGND | E | | GD03854 | S.. | E | | 150-154, 275-276 |
| 010 | 20 | PA | | | 11-7 | 52-35-11 | D04314P | | | 15 | GD00456 | S.. | E | | 050-099 |
| 010 | 20 | PA | | | 8-7 | 52-35-11 | D04314P | | | 15 | GD00456 | S.. | E | | 150-199, 275-299 |
| 011 | 20 | PA | | | 22-0 | 52-35-11 | D04312P | | | 11 | D04314P | | | | 050-099 |
| 011 | 20 | PA | | | 21-9 | 52-35-11 | D04312P | | | 11 | D04314P | | | | 150-199, 275-299 |
| 012 | 20 | PA | | | 22-0 | 52-35-11 | D04312P | | | 12 | D04314P | | | | 050-099 |
| 012 | 20 | PA | | | 21-9 | 52-35-11 | D04312P | | | 12 | D04314P | | | | 150-199, 275-299 |
| 013 | 20 | PA | | | 22-0 | 52-35-11 | D04312P | | | 13 | D04314P | | | | 050-099 |
| 013 | 20 | PA | | | 21-9 | 52-35-11 | D04312P | | | 13 | D04314P | | | | 150-199, 275-299 |
| 014 | 20 | PA | | | 16-4 | 52-35-11 | D04312P | | | 14 | D01998 | | | 1 | 050-099 |
| 014 | 20 | PA | | | 16-5 | 52-35-11 | D04312P | | | 14 | D01998 | | | 1 | 150-199, 275-299 |
| 015 | 20 | PA | | | 16-4 | 52-35-11 | D04312P | | | 15 | D01998 | | | 3 | 050-099 |
| 015 | 20 | PA | | | 16-5 | 52-35-11 | D04312P | | | 15 | D01998 | | | 3 | 150-199, 275-299 |
| 016 | 20 | PA | | | 16-4 | 52-35-11 | D04312P | | | 16 | D01998 | | | 2 | 050-099 |
| 016 | 20 | PA | | | 16-5 | 52-35-11 | D04312P | | | 16 | D01998 | | | 2 | 150-199, 275-299 |
| 017 | 20 | PA | | | 22-0 | 33-31-61 | D04312P | | | 17 | D04314P | | | 17 | 050-099 |
| 017 | 20 | PA | | | 21-9 | 33-31-61 | D04312P | | | 17 | D04314P | | | 17 | 150-199, 275-299 |
| 018 | 20 | PA | | | 29-9 | 33-31-61 | D04312P | | | 18 | L00138 | 28V | E | | 050-099 |
| 018 | 20 | PA | | | 29-7 | 33-31-61 | D04312P | | | 18 | L00138 | 28V | E | | 150-199, 275-299 |
| 019 | 18 | PA | | | 14-1 | 33-37-21 | D04312P | | | 21 | SM00001 | | W | | 050-099 |
| 019 | 16 | PA | | | 24-11 | 33-37-21 | D04312P | | | 21 | SM00001 | | W | | 150-199, 275-299 |
| 020 | 20 | PA | | | 22-0 | 33-37-21 | D04312P | | | 20 | D04314P | | | 20 | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0662 | 286T0662 | | | AFT CARGO DOOR AND LIGHTS (continued) | | | | | | | | | | | | |
| 020 | 18 | | PA | 21-9 | 33-37-21 | D04312P | 20 | DL | | D04314P | 19 | DK | | 150-199, 275-299 | | |
| 021 | 20 | | PA | 55-5 | 33-31-61 | D04312P | 19 | | | S00379 | 2 | C | | 050-099 | | |
| 021 | 20 | | PA | 76-9 | 33-31-61 | D04312P | 19 | | | S00379 | 2 | C | | 150-199 | | |
| 023 | 18 | | PA | 50-5 | 33-37-21 | D04312P | 23 | | | L00550 | =P | C | * | 050-099 | | |
| 023 | 16 | | PA | 72-4 | 33-37-21 | D04312P | 23 | | | L00550 | =P | C | * | 150-199, 275-299 | | |
| 025 | 20 | | PA | 55-5 | 33-37-21 | D04312P | 25 | | | S00430 | 1 | C | | 050-099 | | |
| 025 | 16 | | PA | 76-11 | 33-37-21 | D04312P | 24 | FL | | S00430 | 1 | C | | 150-199, 275-299 | | |
| 026 | 20 | | PA | 55-5 | 33-37-21 | D04312P | 26 | | | S00430 | 3 | C | | 050-099 | | |
| 026 | 16 | | PA | 76-11 | 33-37-21 | D04312P | 26 | FL | | S00430 | 3 | C | | 150-199, 275-299 | | |
| 027 | 18 | | PA | 55-5 | 33-37-21 | D04312P | 27 | DL | | S00430 | 2 | C | | 050-099 | | |
| 027 | 16 | | PA | 76-11 | 33-37-21 | D04312P | 27 | FL | | S00430 | 2 | C | | 150-199, 275-299 | | |
| 031 | 18 | | PA | 22-2 | 33-37-21 | SM00001 | | | W | SM00002 | | W | | 050-099 | | |
| 031 | 16 | | PA | 22-7 | 33-37-21 | SM00001 | | | W | SM00002 | | W | | 150-199, 275-299 | | |
| 032 | 18 | | PA | 42-3 | 33-37-21 | SM00002 | | | W | SM00003 | | W | | 050-099 | | |
| 032 | 16 | | PA | 18-0 | 33-37-21 | SM00002 | | | W | SM00003 | | W | | 150-199, 275-299 | | |
| 033 | 18 | | PA | 7-10 | 33-37-21 | L00548 | | =P | C | SM00001 | | W | | 050-099 | | |
| 033 | 16 | | PA | 8-4 | 33-37-21 | L00548 | | =P | C | SM00001 | | W | | 150-199, 275-299 | | |
| 034 | 18 | | PA | 1-5 | 33-37-21 | L00548 | | =G | C | GD00544 | A.. | E | | 050-099 | | |
| 034 | 16 | | PA | 1-7 | 33-37-21 | L00548 | | =G | C | GD00544 | A.. | E | | 150-199, 275-299 | | |
| 035 | 18 | | PA | 9-1 | 33-37-21 | L00548 | | =P | C | L00549 | =P | C | | 050-099 | | |
| 035 | 16 | | PA | 9-1 | 33-37-21 | L00548 | | =P | C | L00549 | =P | C | | 150-199, 275-299 | | |
| 036 | 18 | | PA | 1-4 | 33-37-21 | L00549 | | =G | C | GD00546 | A.. | E | | 050-099 | | |
| 036 | 16 | | PA | 1-5 | 33-37-21 | L00549 | | =G | C | GD00546 | A.. | E | | 150-199, 275-299 | | |
| 038 | 18 | | PA | 1-6 | 33-37-21 | L00550 | | =G | C | GD00548 | A.. | E | | 050-099 | | |
| 038 | 16 | | PA | 1-6 | 33-37-21 | L00550 | | =G | C | GD00548 | A.. | E | | 150-199, 275-299 | | |
| 039 | 18 | | PA | 8-7 | 33-37-21 | L00550 | | =P | C | L00551 | =P | C | * | 050-099 | | |
| 039 | 16 | | PA | 8-6 | 33-37-21 | L00550 | | =P | C | L00551 | =P | C | * | 150-199, 275-299 | | |
| 040 | 18 | | PA | 1-5 | 33-37-21 | L00551 | | =G | C | GD00550 | A.. | E | | 050-099 | | |
| 040 | 16 | | PA | 1-5 | 33-37-21 | L00551 | | =G | C | GD00550 | A.. | E | | 150-199, 275-299 | | |
| 041 | 18 | | PA | 20-2 | 33-37-21 | L00552 | | =P | C | SM00002 | | W | | 050-099 | | |
| 041 | 16 | | PA | 31-7 | 33-37-21 | L00552 | | =P | C | SM00002 | | W | | 150-199, 275-299 | | |
| 042 | 18 | | PA | 1-5 | 33-37-21 | L00552 | | =G | C | GD00552 | A.. | E | | 050-099 | | |
| 042 | 16 | | PA | 1-5 | 33-37-21 | L00552 | | =G | C | GD00552 | A.. | E | | 150-199, 275-299 | | |
| 043 | 18 | | PA | 8-9 | 33-37-21 | L00553 | | =P | C | L00552 | =P | C | * | 050-099 | | |
| 043 | 16 | | PA | 8-7 | 33-37-21 | L00552 | | =P | C | L00553 | =P | C | | 150-199, 275-299 | | |
| 044 | 18 | | PA | 1-6 | 33-37-21 | L00553 | | =G | C | GD00554 | A.. | E | | 050-099 | | |
| 044 | 16 | | PA | 1-5 | 33-37-21 | L00553 | | =G | C | GD00554 | A.. | E | | 150-199, 275-299 | | |
| 045 | 18 | | PA | 8-8 | 33-37-21 | L00554 | | =P | C | L00555 | =P | C | * | 050-099 | | |
| 045 | 16 | | PA | 8-7 | 33-37-21 | L00554 | | =P | C | L00555 | =P | C | * | 150-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0662 | 286T0662 | | | AFT CARGO DOOR AND LIGHTS (continued) | | | | | | | | | | | | |
| 046 | 18 | PA | | 1-6 | 33-37-21 | L00554 | =G | C | | | GD00556 | A.. | E | | 050-099 | |
| 046 | 16 | PA | | 1-7 | 33-37-21 | L00554 | =G | C | | | GD00556 | A.. | E | | 150-199, 275-299 | |
| 047 | 18 | PA | | 12-7 | 33-37-21 | L00555 | =P | C | * | | SM00004 | | W | | 050-099 | |
| 047 | 16 | PA | | 13-11 | 33-37-21 | L00555 | =P | C | * | | SM00004 | | W | | 150-199, 275-299 | |
| 048 | 18 | PA | | 1-5 | 33-37-21 | L00555 | =G | C | | | GD00558 | A.. | E | | 050-099 | |
| 048 | 16 | PA | | 1-5 | 33-37-21 | L00555 | =G | C | | | GD00558 | A.. | E | | 150-199, 275-299 | |
| 049 | 18 | PA | | 7-0 | 33-37-21 | L00556 | =P | C | | | SM00003 | | W | | 050-099 | |
| 049 | 16 | PA | | 76-1 | 33-37-21 | L00556 | =P | C | | | SM00003 | | W | | 150-199, 275-299 | |
| 050 | 18 | PA | | 1-3 | 33-37-21 | L00556 | =G | C | | | GD00560 | A.. | E | | 050-099 | |
| 050 | 16 | PA | | 1-9 | 33-37-21 | L00556 | =G | C | | | GD00560 | A.. | E | | 150-199, 275-299 | |
| 053 | 18 | PA | | 62-7 | 33-37-21 | L00557 | =P | C | | | SM00003 | | W | | 050-099 | |
| 053 | 16 | PA | | 14-4 | 33-37-21 | L00557 | =P | C | | | SM00003 | | W | | 150-199, 275-299 | |
| 054 | 18 | PA | | 2-9 | 33-37-21 | L00557 | =G | C | | | GD00562 | A.. | E | | 050-099 | |
| 054 | 16 | PA | | 2-2 | 33-37-21 | L00557 | =G | C | | | GD00562 | A.. | E | | 150-199, 275-299 | |
| 057 | 18 | PA | | 8-11 | 33-37-21 | L00558 | =P | C | | | L00560 | =P | C | * | 050-099 | |
| 057 | 16 | PA | | 8-11 | 33-37-21 | L00558 | =P | C | | | L00560 | =P | C | * | 150-199, 275-299 | |
| 058 | 18 | PA | | 1-7 | 33-37-21 | L00558 | =G | C | | | GD00566 | A.. | E | | 050-099 | |
| 058 | 16 | PA | | 1-7 | 33-37-21 | L00558 | =G | C | | | GD00566 | A.. | E | | 150-199, 275-299 | |
| 059 | 18 | PA | | 67-3 | 33-37-21 | L00560 | =P | C | * | | SM00004 | | W | | 050-099 | |
| 059 | 16 | PA | | 86-7 | 33-37-21 | L00560 | =P | C | * | | SM00004 | | W | | 150-199, 275-299 | |
| 060 | 18 | PA | | 1-5 | 33-37-21 | L00560 | =G | C | | | GD00568 | A.. | E | | 050-099 | |
| 060 | 16 | PA | | 1-3 | 33-37-21 | L00560 | =G | C | | | GD00568 | A.. | E | | 150-199, 275-299 | |
| 061 | 18 | PA | | 14-7 | 33-37-21 | SM00004 | | W | | | L00551 | =P | C | * | 050-099 | |
| 061 | 16 | PA | | 13-6 | 33-37-21 | SM00004 | | W | | | L00551 | =P | C | * | 150-199, 275-299 | |
| 063 | 20 | PA | | 16-9 | 33-31-61 | D04314P | | 18 | | | GD00300 | A.. | 2 | | 050-099 | |
| 063 | 20 | PA | | 16-2 | 33-31-61 | D04314P | | 18 | | | GD00300 | A.. | 2 | | 150-156, 162-166, 275-276 | |
| 063 | 20 | PA | | 16-3 | 33-31-61 | D04314P | | 18 | | | GD00300 | A.. | 2 | | 157, 167-199, 277-299 | |
| 064 | 20 | PA | | 16-9 | 33-37-21 | D04314P | | 21 | | | GD00300 | A.. | 2 | | 050-099 | |
| 064 | 18 | PA | | 16-2 | 33-37-21 | D04314P | | 21 | DK | | GD00300 | A.. | 2 | | 150-156, 162-166, 275-276 | |
| 064 | 18 | PA | | 16-3 | 33-37-21 | D04314P | | 21 | DK | | GD00300 | A.. | 2 | | 157, 167-199, 277-299 | |
| 065 | 20 | PA | | 2-3 | 33-31-61 | L00138 | | RTN | E | | GD00478 | A.. | E | | 050-099, 155-199, 277-299 | |
| 065 | 20 | PA | | 2-3 | 33-31-61 | L00138 | | GND | E | | GD00478 | A.. | E | | 150-154, 275-276 | |
| 071 | 20 | PA | | 11-0 | 33-31-61 | S00379 | | 3 | C | * | L00139 | 115V | E | | 050-099 | |
| 071 | 20 | PA | | 10-1 | 33-31-61 | L00139 | | 115V | E | | S00379 | 3 | C | * | 150-199 | |
| 072 | 20 | PA | | 5-4 | 33-31-61 | L00139 | | RTN | E | | GD00408 | A.. | 2 | | 050-099, 150-199 | |
| 073 | 20 | PA | | 86-1 | 33-31-61 | S00379 | | 3 | C | * | L00140 | 115V | E | | 050-099 | |

WIRE LIST
D280T132

91-21-11
Section W0660
Page 5
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|--------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0662 | 286T0662 | AFT CARGO DOOR AND LIGHTS (continued) | | | | | | | | | | | | | | |
| 073 | 20 | PA | | 106-11 | 33-31-61 | L00140 | 115V | E | | S00379 | 3 | C | * | 150-199 | | |
| 074 | 20 | PA | | 1-10 | 33-31-61 | L00140 | RTN | E | | GD00482 | A.. | E | | 050-099, 150-199 | | |
| 077 | 16 | PA | | 16-4 | 33-37-21 | L00830 | =P | C | * | SM00002 | | W | | 150-199, 275-299 | | |
| 078 | 16 | PA | | 8-7 | 33-37-21 | L00829 | =P | C | | L00830 | =P | C | * | 150-199, 275-299 | | |
| 079 | 16 | PA | | 1-7 | 33-37-21 | L00829 | =G | C | | GD05124 | A.. | E | | 150-199, 275-299 | | |
| 080 | 16 | PA | | 1-6 | 33-37-21 | L00830 | =G | C | | GD05126 | A.. | E | | 150-199, 275-299 | | |
| 081 | 16 | PA | | 1-6 | 33-37-21 | L00832 | =G | C | | GD05130 | A.. | E | | 150-199, 275-299 | | |
| 082 | 16 | PA | | 19-3 | 33-37-21 | L00831 | =P | C | * | SM00004 | | W | | 150-199, 275-299 | | |
| 083 | 16 | PA | | 9-0 | 33-37-21 | L00832 | =P | C | | L00831 | =P | C | * | 150-199, 275-299 | | |
| 084 | 16 | PA | | 1-7 | 33-37-21 | L00831 | =G | C | | GD05128 | A.. | E | | 150-199, 275-299 | | |
| 201B | 24 | PL | A | 22-0 | 52-71-13 | D04312P | | 1 | | D04314P | 1 | | | 050-099 | | |
| 201B | 24 | PL | A | 21-9 | 52-71-13 | D04312P | | 1 | | D04314P | 1 | | | 150-199, 275-299 | | |
| 201R | 24 | PL | A | 0-0 | 52-71-13 | D04312P | | 2 | | D04314P | 2 | | | ALL | | |
| 202B | 24 | PL | B | 22-0 | 52-35-13 | D04312P | | 3 | | D04314P | 3 | | | 050-099 | | |
| 202B | 24 | PL | B | 21-9 | 52-35-13 | D04312P | | 3 | | D04314P | 3 | | | 150-199, 275-299 | | |
| 202R | 24 | PL | B | 0-0 | 52-35-13 | D04312P | | 4 | | D04314P | 4 | | | ALL | | |
| 203B | 24 | PL | C | 22-0 | 52-35-13 | D04312P | | 5 | | D04314P | 5 | | | 050-099 | | |
| 203B | 24 | PL | C | 21-9 | 52-35-13 | D04312P | | 5 | | D04314P | 5 | | | 150-199, 275-299 | | |
| 203R | 24 | PL | C | 0-0 | 52-35-13 | D04312P | | 6 | | D04314P | 6 | | | ALL | | |
| 204B | 24 | PL | D | 22-0 | 52-35-13 | D04312P | | 7 | | D04314P | 7 | | | 050-099 | | |
| 204B | 24 | PL | D | 21-9 | 52-35-13 | D04312P | | 7 | | D04314P | 7 | | | 150-199, 275-299 | | |
| 204R | 24 | PL | D | 0-0 | 52-35-13 | D04312P | | 8 | | D04314P | 8 | | | ALL | | |
| 205B | 24 | PL | E | 22-0 | 52-35-13 | D04312P | | 9 | | D04314P | 9 | | | 050-099 | | |
| 205R | 24 | PL | E | 0-0 | 52-35-13 | D04312P | | 10 | | D04314P | 10 | | | 050-099 | | |
| W0664 | 286T0664 | FWD CARGO COMPARTMENT SMOKE DET 2 | | | | | | | | | | | | | | |
| 001R | 24 | PP | | 3-0 | 26-16-11 | D01462 | | 4 | | D06944J | 1 | | | ALL | | |
| 003R | 20 | PH | | 3-0 | 26-16-11 | D01462 | | 5 | | D06944J | 3 | | | ALL | | |
| 005R | 20 | PH | | 3-0 | 26-16-11 | D01462 | | 9 | | D06944J | 5 | | | ALL | | |
| 007R | 20 | PH | | 3-0 | 26-16-11 | D01462 | | 10 | | D06944J | 7 | | | ALL | | |
| 009R | 24 | PP | | 3-0 | 26-16-11 | D01462 | | 11 | | D06944J | 9 | | | ALL | | |
| 011R | 24 | PP | | 3-0 | 26-16-11 | D01462 | | 12 | | D06944J | 11 | | | ALL | | |
| W0665 | 286T0665 | E2-5 TO FWD,MID,AND AFT ATTENDANTS SPEAKER AND CHIMES | | | | | | | | | | | | | | |
| 001 | 22 | PA | | 14-1 | 23-42-11 | SM00001 | | S | | D04123J | 1 | | | 050-099 | | |
| 001 | 22 | PA | | 43-3 | 23-42-11 | SM00001 | | S | | D04123J | 1 | | | 150-199 | | |
| 001 | 22 | PA | | 2-5 | 23-42-11 | SM00001 | | S | | D05337J | 1 | | | 275-299 | | |
| 002 | 22 | PA | | 16-5 | 23-42-11 | SM00001 | | S | | D04121J | 1 | | | 050-099 | | |
| 002 | 22 | PA | | 45-10 | 23-42-11 | SM00001 | | S | | D04121J | 1 | | | 150-199 | | |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0665 | 286T0665 | | | E2-5 TO FWD,MID,AND AFT ATTENDANTS SPEAKER AND CHIMES (continued) | | | | | | | | | | | |
| 002 | 22 | | PA | | 23-0 | 23-42-11 | SM00001 | | S | | D05335J | | 1 | | 275-299 |
| 003 | 22 | | PA | | 120-9 | 23-42-11 | SM00001 | | S | | D04647J | | 3 | | 050-099 |
| 003 | 22 | | PA | | 112-5 | 23-42-11 | SM00001 | | S | | D04647J | | 3 | | 150-199 |
| 003 | 22 | | PA | | 142-0 | 23-42-11 | SM00001 | | S | | D04647J | | 3 | | 275-299 |
| 004 | 22 | | PA | | 4-9 | 23-42-11 | SM00002 | | S | | L00195 | L1 | C | | 050-099 |
| 004 | 22 | | PA | | 15-9 | 23-42-11 | SM00002 | | S | | D05329J | | 1 | | 150-157 |
| 004 | 22 | | PA | | 17-0 | 23-42-11 | SM00002 | | S | | L00195 | L1 | C | | 162-199 |
| 004 | 22 | | PA | | 4-0 | 23-42-11 | SM00002 | | S | | D05329J | | 1 | | 275-299 |
| 005 | 22 | | PA | | 8-6 | 23-42-11 | SM00002 | | S | | L00194 | L1 | C | | 050-099 |
| 005 | 22 | | PA | | 13-7 | 23-42-11 | SM00002 | | S | | D05327J | | 1 | | 150-157 |
| 005 | 22 | | PA | | 14-7 | 23-42-11 | SM00002 | | S | | L00194 | L1 | C | | 162-199 |
| 005 | 22 | | PA | | 7-7 | 23-42-11 | SM00002 | | S | | D05327J | | 1 | | 275-299 |
| 006 | 22 | | PA | | 40-3 | 23-42-11 | SM00002 | | S | | D04647J | | 4 | | 050-099 |
| 006 | 22 | | PA | | 29-7 | 23-42-11 | SM00002 | | S | | D04647J | | 4 | | 150-199 |
| 006 | 22 | | PA | | 40-9 | 23-42-11 | SM00002 | | S | | D04647J | | 4 | | 275-299 |
| 007 | 22 | | PA | | 37-1 | 23-42-11 | SM00003 | | S | | D06055J | | 1 | | 050-099 |
| 007 | 22 | | PA | | 8-7 | 23-42-11 | SM00003 | | S | | D06055J | | 1 | | 150-154, 156, 162-199 |
| 007 | 22 | | PA | | 10-0 | 23-42-11 | SM00003 | | S | | L00211 | L1 | C | | 155, 157 |
| 007 | 22 | | PA | | 49-6 | 23-42-11 | SM00003 | | S | | L00211 | =P | \$ | | 275-276 |
| 007 | 22 | | PA | | 10-4 | 23-42-11 | SM00003 | | S | | D06055J | | 1 | | 277-278 |
| 007 | 22 | | PA | | 13-11 | 23-42-11 | SM00048 | | S | | D06055J | | 1 | | 280-299 |
| 008 | 22 | | PA | | 39-5 | 23-42-11 | SM00003 | | S | | D06057J | | 1 | | 050-099 |
| 008 | 22 | | PA | | 10-10 | 23-42-11 | SM00003 | | S | | D06057J | | 1 | | 150-154, 156, 162-199 |
| 008 | 22 | | PA | | 12-11 | 23-42-11 | SM00003 | | S | | L00196 | L1 | C | | 155, 157 |
| 008 | 22 | | PA | | 52-10 | 23-42-11 | SM00003 | | S | | L00196 | =P | \$ | | 275-276 |
| 008 | 22 | | PA | | 12-3 | 23-42-11 | SM00003 | | S | | D06057J | | 1 | | 277-278 |
| 008 | 22 | | PA | | 15-10 | 23-42-11 | SM00049 | | S | | D06057J | | 1 | | 280-299 |
| 009 | 22 | | PA | | 44-3 | 23-42-11 | SM00003 | | S | | D04647J | | 5 | | 050-099 |
| 009 | 22 | | PA | | 79-0 | 23-42-11 | SM00003 | | S | | D04647J | | 5 | | 150-199, 277-278 |
| 009 | 22 | | PA | | 44-8 | 23-42-11 | SM00003 | | S | | D04647J | | 5 | | 275-276 |
| 009 | 22 | | PA | | 58-2 | 23-42-11 | SM00003 | | S | | D04647J | | 5 | | 280-299 |
| 010 | 24 | | PK | | 16-4 | 23-34-13 | SM00044 | | S | | L00580 | L3 | C | | 050-099 |
| 010 | 22 | | PA | | 7-9 | 23-34-13 | SM00044 | | S | | D05329J | | 2 | | 150-157 |
| 010 | 22 | | PA | | 9-0 | 23-34-13 | SM00044 | | S | | L00580 | L3 | C | | 162-199 |
| 011 | 24 | | PK | | 17-6 | 23-34-13 | SM00044 | | S | | D04397J | | 2 | | 050-099 |
| 011 | 24 | | PK | | 8-5 | 23-34-13 | SM00044 | | S | | D04397J | | 2 | | 150-199 |
| 012 | 24 | | PK | | 62-4 | 23-34-13 | SM00004 | | S | | D06061J | | 2 | | 050-099 |
| 012 | 24 | | PK | | 75-1 | 23-34-13 | SM00004 | | S | | D06061J | | 2 | | 150-199 |
| 012 | 24 | | PK | | 49-6 | 23-34-13 | SM00004 | | S | | L00688 | =P | \$ | | 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|----|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0665 | 286T0665 | | | E2-5 TO FWD,MID,AND AFT ATTENDANTS SPEAKER AND CHIMES (continued) | | | | | | | | | | | | | |
| 012 | 24 | | PK | 10-4 | 23-34-13 | SM00004 | | | | S | | | D06055J | 2 | | | 277-299 |
| 013 | 24 | | PK | 90-7 | 23-34-13 | SM00004 | | | | S | | | D04123J | 2 | | | 050-099 |
| 013 | 24 | | PK | 111-0 | 23-34-13 | SM00004 | | | | S | | | D04123J | 2 | | | 150-199 |
| 013 | 24 | | PK | 100-3 | 23-34-13 | SM00004 | | | | S | | | D05337J | 2 | | | 275-276 |
| 013 | 24 | | PK | 66-6 | 23-34-13 | SM00004 | | | | S | | | D05337J | 2 | | | 277-299 |
| 014 | 24 | | PK | 44-3 | 23-34-13 | SM00004 | | | | S | | | D04647J | 8 | | | 050-099 |
| 014 | 24 | | PK | 44-8 | 23-34-13 | SM00004 | | | | S | | | D04647J | 8 | | | 150-199, 275-276 |
| 014 | 24 | | PK | 79-0 | 23-34-13 | SM00004 | | | | S | | | D04647J | 8 | | | 277-299 |
| 015 | 24 | | PK | 64-1 | 23-34-13 | SM00005 | | | | S | | | D06059J | 2 | | | 050-099 |
| 015 | 24 | | PK | 77-0 | 23-34-13 | SM00005 | | | | S | | | D06059J | 2 | | | 150-199 |
| 015 | 24 | | PK | 52-10 | 23-34-13 | SM00005 | | | | S | | | L00687 | =P | \$ | | 275-276 |
| 015 | 24 | | PK | 12-3 | 23-34-13 | SM00005 | | | | S | | | D06057J | 2 | | | 277-299 |
| 016 | 24 | | PK | 92-11 | 23-34-13 | SM00005 | | | | S | | | D04121J | 2 | | | 050-099 |
| 016 | 24 | | PK | 113-7 | 23-34-13 | SM00005 | | | | S | | | D04121J | 2 | | | 150-199 |
| 016 | 24 | | PK | 120-4 | 23-34-13 | SM00005 | | | | S | | | D05335J | 2 | | | 275-276 |
| 016 | 24 | | PK | 86-6 | 23-34-13 | SM00005 | | | | S | | | D05335J | 2 | | | 277-299 |
| 017 | 24 | | PK | 44-3 | 23-34-13 | SM00005 | | | | S | | | D04647J | 9 | | | 050-099 |
| 017 | 24 | | PK | 44-8 | 23-34-13 | SM00005 | | | | S | | | D04647J | 9 | | | 150-199, 275-276 |
| 017 | 24 | | PK | 79-0 | 23-34-13 | SM00005 | | | | S | | | D04647J | 9 | | | 277-299 |
| 018 | 22 | | PA | 12-3 | 33-25-11 | SP00568 | | | | S | | | L00565 | L2 | C | | 050-099 |
| 018 | 22 | | PA | 11-9 | 33-25-11 | SP00568 | | | | S | | | D05327J | 3 | | | 150-157, 275-299 |
| 018 | 22 | | PA | 12-9 | 33-25-11 | SP00568 | | | | S | | | L00565 | L2 | C | | 162-199 |
| 019 | 22 | | PA | 5-0 | 33-25-11 | SP03700 | | | | S | | | L00564 | L2 | C | | 050-099 |
| 019 | 22 | | PA | 4-10 | 33-25-11 | SP03700 | | | | S | | | D05329J | 3 | | | 150-157 |
| 019 | 22 | | PA | 5-2 | 33-25-11 | SP03700 | | | | S | | | L00564 | L2 | C | | 162-199 |
| 019 | 22 | | PA | 4-10 | 33-25-11 | SP00568 | | | | S | | | D05329J | 3 | | | 275-299 |
| 020 | 22 | | PA | 39-2 | 33-25-11 | SP03698 | | | | S | | | D06059J | 3 | | | 050-099 |
| 020 | 22 | | PA | 40-11 | 33-25-11 | SP03698 | | | | S | | | D06059J | 3 | | | 150-199 |
| 020 | 22 | | PA | 19-3 | 33-25-11 | SP00570 | | | | S | | | L01161 | =P | \$ | | 275-276 |
| 021 | 22 | | PA | 50-0 | 33-25-11 | SP00574 | | | | S | | | D06061J | 3 | | | 050-099 |
| 021 | 22 | | PA | 39-1 | 33-25-11 | SP00572 | | | | S | | | D06061J | 3 | | | 150-199 |
| 021 | 22 | | PA | 16-5 | 33-25-11 | SP03214 | | | | S | | | L01160 | =P | \$ | | 275-276 |
| 022 | 22 | | PA | 18-1 | 33-25-11 | SP00574 | | | | S | | | D04123J | 3 | | | 050-099 |
| 022 | 22 | | PA | 75-6 | 33-25-11 | SP00572 | | | | S | | | D04123J | 3 | | | 150-199 |
| 022 | 22 | | PA | 3-8 | 33-25-11 | SP00576 | | | | S | | | D05337J | 3 | | | 275-299 |
| 023 | 22 | | PA | 32-3 | 33-25-11 | SP03698 | | | | S | | | D04121J | 3 | | | 050-099 |
| 023 | 22 | | PA | 78-0 | 33-25-11 | SP03698 | | | | S | | | D04121J | 3 | | | 150-199 |
| 023 | 22 | | PA | 39-2 | 33-25-11 | SP00574 | | | | S | | | D05335J | 3 | | | 275-299 |
| 024 | 22 | | PA | 32-6 | 23-42-11 | SM00003 | | | | S | | | D05331J | 1 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 8

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|-----------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0665 | 286T0665 | | | E2-5 TO FWD,MID,AND AFT ATTENDANTS SPEAKER AND CHIMES (continued) | | | | | | | | | | | | | | |
| 024 | 22 | PA | | | 16-1 | 23-42-11 | SM00003 | | | | S | | | D06482J | 1 | | | 150-199 |
| 024 | 22 | PA | | | 41-0 | 23-42-11 | SM00003 | | | | S | | | SM00055 | | S | | 275-276 |
| 024 | 22 | PA | | | 10-1 | 23-42-11 | SM00003 | | | | S | | | SM00055 | | S | | 277-278 |
| 024 | 22 | PA | | | 27-1 | 23-42-11 | SM00003 | | | | S | | | D05331J | 1 | | | 280-299 |
| 025 | 24 | PK | | | 9-11 | 23-34-13 | D05331J | | 2 | | | | | SM00033 | | S | | 275-278 |
| 025 | 24 | PK | | | 13-4 | 23-34-13 | D05331J | | 2 | | | | | SM00033 | | S | | 280-299 |
| 026 | 22 | PA | | | 23-0 | 33-25-11 | SP00572 | | | | S | | | D05331J | 3 | | | 050-099 |
| 026 | 22 | PA | | | 21-3 | 33-25-11 | SP00570 | | | | S | | | D05331J | 3 | | | 275-276 |
| 026 | 22 | PA | | | 12-4 | 33-25-11 | SM00057 | | | | S | | | D05331J | 3 | | | 277-299 |
| 027 | 24 | PK | | | 9-11 | 23-34-13 | D05331J | | 5 | | | | | SM00034 | | S | | 275-278 |
| 027 | 24 | PK | | | 13-4 | 23-34-13 | D05331J | | 5 | | | | | SM00034 | | S | | 280-299 |
| 028 | 22 | PA | | | 23-0 | 33-25-11 | SP00570 | | | | S | | | D05331J | 6 | | | 050-099 |
| 028 | 22 | PA | | | 21-3 | 33-25-11 | SP03214 | | | | S | | | D05331J | 6 | | | 275-276 |
| 028 | 22 | PA | | | 12-4 | 33-25-11 | SM00056 | | | | S | | | D05331J | 6 | | | 277-299 |
| 029 | 20 | PA | | | 22-7 | 23-42-11 | GD00934 | | | D.. | 2 | | | D05331J | 4 | | | 050-099 |
| 029 | 20 | PA | | | 3-2 | 23-42-11 | GD01950 | | | D.. | 2 | | | D06482J | 4 | | | 150-199 |
| 029 | 20 | PA | | | 4-1 | 23-42-11 | GD04198 | | | D.. | 2 | | | D05331J | 4 | | | 275-299 |
| 030 | 20 | PA | | | 5-4 | 23-42-11 | GD03932 | | | D.. | 2 | | | L00194 | 3 | C | | 050-099 |
| 030 | 20 | PA | | | 4-5 | 23-42-11 | GD03932 | | | D.. | 2 | | | D05327J | 4 | | | 150-157, 275-299 |
| 030 | 20 | PA | | | 6-2 | 23-42-11 | GD03932 | | | D.. | 2 | | | L00194 | 3 | C | | 162-199 |
| 031 | 20 | PA | | | 7-5 | 23-42-11 | GD01114 | | | D.. | 2 | | | L00195 | 3 | C | | 050-099 |
| 031 | 20 | PA | | | 4-11 | 23-42-11 | GD01114 | | | D.. | 2 | | | D05329J | 4 | | | 150-157, 275-299 |
| 031 | 20 | PA | | | 7-11 | 23-42-11 | GD01114 | | | D.. | 2 | | | L00195 | 3 | C | | 162-199 |
| 032 | 20 | PA | | | 1-11 | 23-42-11 | GD01950 | | | D.. | 2 | | | D06057J | 4 | | | 050-099 |
| 032 | 20 | PA | | | 1-9 | 23-42-11 | GD00934 | | | D.. | 2 | | | D06057J | 4 | | | 150-154, 156, 162-199 |
| 032 | 20 | PA | | | 12-11 | 23-42-11 | GD00934 | | | D.. | 2 | | | L00196 | 3 | C | | 155, 157 |
| 032 | 20 | PA | | | 8-5 | 23-42-11 | GD01944 | | | D.. | 2 | | | L00196 | =G | \$ | | 275-276 |
| 032 | 20 | PA | | | 4-4 | 23-42-11 | GD01944 | | | D.. | 2 | | | D06057J | 4 | | | 277-278 |
| 032 | 20 | PA | | | 1-6 | 23-42-11 | GD01944 | | | D.. | 2 | | | D06057J | 4 | | | 280-299 |
| 033 | 20 | PA | | | 4-4 | 23-42-11 | GD01950 | | | D.. | 2 | | | D06055J | 4 | | | 050-099 |
| 033 | 20 | PA | | | 4-0 | 23-42-11 | GD00934 | | | D.. | 2 | | | D06055J | 4 | | | 150-154, 156, 162-199 |
| 033 | 20 | PA | | | 9-11 | 23-42-11 | GD00934 | | | D.. | 2 | | | L00211 | 3 | C | | 155, 157 |
| 033 | 20 | PA | | | 9-1 | 23-42-11 | GD02544 | | | D.. | 2 | | | L00211 | =G | \$ | | 275-276 |
| 033 | 20 | PA | | | 1-9 | 23-42-11 | GD02544 | | | D.. | 2 | | | D06055J | 4 | | | 277-299 |
| 034 | 20 | PA | | | 18-6 | 23-42-11 | GD00026 | | | D.. | 2 | | | D04121J | 4 | | | 050-099 |
| 034 | 20 | PA | | | 13-4 | 23-42-11 | GD00026 | | | D.. | 2 | | | D04121J | 4 | | | 150-199 |
| 034 | 20 | PA | | | 8-4 | 23-42-11 | GD00026 | | | D.. | 2 | | | D05335J | 4 | | | 275-299 |
| 035 | 20 | PA | | | 14-4 | 23-42-11 | GD00020 | | | D.. | 2 | | | D04123J | 4 | | | 050-099 |
| 035 | 20 | PA | | | 13-9 | 23-42-11 | GD00020 | | | D.. | 2 | | | D04123J | 4 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 9

Mar 14/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0665 | 286T0665 | | | E2-5 TO FWD,MID,AND AFT ATTENDANTS SPEAKER AND CHIMES (continued) | | | | | | | | | | | | |
| 035 | 20 | | PA | 7-9 | 23-42-11 | GD00020 | | D.. | 2 | | | | D05337J | 4 | | 275-299 |
| 036 | 22 | | PA | 8-5 | 23-42-12 | D04647J | | | 10 | | | | SM00015 | | S | 150-199, 275-276 |
| 036 | 22 | | PA | 29-7 | 23-42-12 | D04647J | | | 10 | | | | SM00015 | | S | 277-299 |
| 037 | 24 | | PK | 8-5 | 23-42-12 | D04647J | | | 11 | | | | SM00018 | | S | 150-199, 275-276 |
| 037 | 24 | | PK | 29-7 | 23-42-12 | D04647J | | | 11 | | | | SM00018 | | S | 277-299 |
| 038 | 24 | | PK | 60-3 | 23-42-12 | D04647J | | | 12 | | | | SM00019 | | S | 150-199, 275-276 |
| 038 | 24 | | PK | 75-4 | 23-42-12 | D04647J | | | 12 | | | | SM00019 | | S | 277-278 |
| 038 | 24 | | PK | 71-11 | 23-42-12 | D04647J | | | 12 | | | | SM00019 | | S | 280-299 |
| 039 | 24 | | PK | 147-11 | 23-42-12 | D04647J | | | 13 | | | | SM00020 | | S | 150-199, 275-299 |
| 040 | 22 | | PA | 52-10 | 23-42-12 | SM00015 | | | | | S | | SM00016 | | S | 150-199, 275-276 |
| 040 | 22 | | PA | 46-4 | 23-42-12 | SM00015 | | | | | S | | SM00016 | | S | 277-278 |
| 040 | 22 | | PA | 42-10 | 23-42-12 | SM00015 | | | | | S | | SM00016 | | S | 280-299 |
| 041 | 20 | | PA | 8-9 | 23-42-12 | B00139 | | GRD | C | | | | GD01236 | D.. | 2 | 150-199, 275-299 |
| 042 | 22 | | PA | 43-8 | 23-42-12 | B00139 | | | 28V | C | | | SM00015 | | S | 150-199, 275-276 |
| 042 | 22 | | PA | 22-6 | 23-42-12 | B00139 | | | 28V | C | | | SM00015 | | S | 277-299 |
| 043 | 24 | | PK | 43-8 | 23-42-12 | B00139 | | | H/L | C | | | SM00018 | | S | 150-199, 275-276 |
| 043 | 24 | | PK | 22-6 | 23-42-12 | B00139 | | | H/L | C | | | SM00018 | | S | 277-299 |
| 044 | 20 | | PA | 5-2 | 23-42-12 | B00144 | | GRD | C | | | | GD00002 | D.. | 2 | 150-199, 275-299 |
| 045 | 22 | | PA | 42-2 | 23-42-12 | B00144 | | | 28V | C | | | SM00015 | | S | 150-199, 275-276 |
| 045 | 22 | | PA | 21-1 | 23-42-12 | B00144 | | | 28V | C | | | SM00015 | | S | 277-299 |
| 046 | 24 | | PK | 42-2 | 23-42-12 | B00144 | | | H/L | C | | | SM00018 | | S | 150-199, 275-276 |
| 046 | 24 | | PK | 21-1 | 23-42-12 | B00144 | | | H/L | C | | | SM00018 | | S | 277-299 |
| 047 | 22 | | PA | 89-3 | 23-42-12 | SM00016 | | | | S | | | SM00017 | | S | 150-199, 275-276 |
| 047 | 22 | | PA | 74-1 | 23-42-12 | SM00016 | | | | S | | | SM00017 | | S | 277-278 |
| 047 | 22 | | PA | 77-7 | 23-42-12 | SM00016 | | | | S | | | SM00017 | | S | 280-299 |
| 048 | 20 | | PA | 3-2 | 23-42-12 | D06482J | | | 14 | | | | GD01950 | D.. | 2 | 150-199 |
| 048 | 20 | | PA | 4-1 | 23-42-12 | D05331J | | | 14 | | | | GD04198 | D.. | 2 | 275-299 |
| 049 | 22 | | PA | 34-10 | 23-42-12 | D06482J | | | 13 | | | | SM00016 | | S | 150-199 |
| 049 | 22 | | PA | 25-0 | 23-42-12 | D05331J | | | 13 | | | | SM00016 | | S | 275-276 |
| 049 | 22 | | PA | 9-11 | 23-42-12 | D05331J | | | 13 | | | | SM00016 | | S | 277-278 |
| 049 | 22 | | PA | 13-4 | 23-42-12 | D05331J | | | 13 | | | | SM00016 | | S | 280-299 |
| 050 | 24 | | PK | 34-10 | 23-42-12 | D06482J | | | 12 | | | | SM00019 | | S | 150-199 |
| 050 | 24 | | PK | 25-0 | 23-42-12 | D05331J | | | 12 | | | | SM00019 | | S | 275-276 |
| 050 | 24 | | PK | 9-11 | 23-42-12 | D05331J | | | 12 | | | | SM00019 | | S | 277-278 |
| 050 | 24 | | PK | 13-4 | 23-42-12 | D05331J | | | 12 | | | | SM00019 | | S | 280-299 |
| 051 | 20 | | PA | 3-2 | 23-42-12 | D06482J | | | 18 | | | | GD01950 | D.. | 2 | 150-199 |
| 051 | 20 | | PA | 4-1 | 23-42-12 | D05331J | | | 18 | | | | GD04198 | D.. | 2 | 275-299 |
| 052 | 22 | | PA | 34-10 | 23-42-12 | D06482J | | | 17 | | | | SM00016 | | S | 150-199 |
| 052 | 22 | | PA | 25-0 | 23-42-12 | D05331J | | | 17 | | | | SM00016 | | S | 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 10

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0665 | 286T0665 | | | E2-5 TO FWD,MID,AND AFT ATTENDANTS SPEAKER AND CHIMES (continued) | | | | | | | | | | | | | | |
| 052 | 22 | PA | | | 9-11 | 23-42-12 | D05331J | | 17 | | | | | SM00016 | | S | | 277-278 |
| 052 | 22 | PA | | | 13-4 | 23-42-12 | D05331J | | 17 | | | | | SM00016 | | S | | 280-299 |
| 053 | 24 | PK | | | 34-10 | 23-42-12 | D06482J | | 16 | | | | | SM00019 | | S | | 150-199 |
| 053 | 24 | PK | | | 25-0 | 23-42-12 | D05331J | | 16 | | | | | SM00019 | | S | | 275-276 |
| 053 | 24 | PK | | | 9-11 | 23-42-12 | D05331J | | 16 | | | | | SM00019 | | S | | 277-278 |
| 053 | 24 | PK | | | 13-4 | 23-42-12 | D05331J | | 16 | | | | | SM00019 | | S | | 280-299 |
| 054 | 20 | PA | | | 14-1 | 23-42-12 | B00147 | | | GRD | C | | | GD00932 | | D.. | 2 | 150-199, 275-299 |
| 055 | 22 | PA | | | 9-3 | 23-42-12 | B00147 | | | 28V | C | | | SM00017 | | S | | 150-199, 275-299 |
| 056 | 24 | PK | | | 9-3 | 23-42-12 | B00147 | | | H/L | C | | | SM00020 | | S | | 150-199, 275-299 |
| 057 | 20 | PA | | | 11-9 | 23-42-12 | B00148 | | | GRD | C | | | GD00932 | | D.. | 2 | 150-199, 275-276, 280-299 |
| 057 | 20 | PA | | | 11-11 | 23-42-12 | B00148 | | | GRD | C | | | GD00932 | | D.. | 2 | 277-278 |
| 058 | 22 | PA | | | 11-7 | 23-42-12 | B00148 | | | 28V | C | | | SM00017 | | S | | 150-199, 275-276, 280-299 |
| 058 | 22 | PA | | | 12-6 | 23-42-12 | B00148 | | | 28V | C | | | SM00017 | | S | | 277-278 |
| 059 | 24 | PK | | | 11-7 | 23-42-12 | B00148 | | | H/L | C | | | SM00020 | | S | | 150-199, 275-276, 280-299 |
| 059 | 24 | PK | | | 12-6 | 23-42-12 | B00148 | | | H/L | C | | | SM00020 | | S | | 277-278 |
| 060 | 24 | PK | | | 51-7 | 23-34-13 | D04647J | | | 15 | | | | B00139 | | HI | C | 150-199, 275-299 |
| 061 | 24 | PK | | | 49-7 | 23-34-13 | D04647J | | | 16 | | | | B00144 | | HI | C | 150-199, 275-299 |
| 062 | 24 | PK | | | 94-1 | 23-34-13 | D04647J | | | 17 | | | | D06482J | | 19 | | 150-199 |
| 062 | 24 | PK | | | 77-3 | 23-34-13 | D04647J | | | 17 | | | | SP00327 | | S | | 275-299 |
| 063 | 24 | PK | | | 94-1 | 23-34-13 | D04647J | | | 18 | | | | D06482J | | 20 | | 150-199 |
| 063 | 24 | PK | | | 77-3 | 23-34-13 | D04647J | | | 18 | | | | SP00329 | | S | | 275-299 |
| 064 | 24 | PK | | | 156-1 | 23-34-13 | D04647J | | | 19 | | | | B00147 | | HI | C | 150-199, 275-299 |
| 065 | 24 | PK | | | 158-6 | 23-34-13 | D04647J | | | 20 | | | | B00148 | | HI | C | 150-199, 275-276, 280-299 |
| 065 | 24 | PK | | | 159-4 | 23-34-13 | D04647J | | | 20 | | | | B00148 | | HI | C | 277-278 |
| 066 | 22 | PA | | | 16-10 | 33-25-11 | D06482J | | | 2 | | | | SP00327 | | S | | 150-199 |
| 066 | 24 | PK | | | 15-0 | 23-34-13 | D05331J | | | 15 | | | | SP00327 | | S | | 275-299 |
| 067 | 22 | PA | | | 16-10 | 33-25-11 | D06482J | | | 3 | | | | SP00329 | | S | | 150-199 |
| 067 | 24 | PK | | | 15-0 | 23-34-13 | D05331J | | | 11 | | | | SP00329 | | S | | 275-299 |
| 068 | 22 | PA | | | 19-4 | 23-42-11 | SM00001 | | | | | S | | D05353J | | 1 | | 050-099 |
| 068 | 20 | PA | | | 10-0 | 23-42-11 | L01055 | | | 3 | | C | | GD04198 | | D.. | 2 | 275-276 |
| 068 | 20 | PA | | | 7-2 | 23-42-11 | L01055 | | | 3 | | C | | GD04198 | | D.. | 2 | 277-278 |
| 069 | 22 | PA | | | 10-0 | 23-42-11 | L01055 | | | L1 | | C | | SM00055 | | S | | 275-276 |
| 069 | 22 | PA | | | 4-11 | 23-42-11 | L01055 | | | L1 | | C | | SM00055 | | S | | 277-278 |
| 070 | 20 | PA | | | 12-7 | 23-42-11 | GD00932 | | | D.. | | 2 | | D05353J | | 4 | | 050-099 |
| 070 | 22 | PA | | | 10-0 | 23-42-11 | L01052 | | | L1 | | C | | SM00055 | | S | | 275-276 |

WIRE LIST
D280T132

91-21-11
Section W0660
Page 11
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|--------|-------|-------------|---------|------|--------|--|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type | Splice | | |
| W0665 | 286T0665 | | | E2-5 TO FWD,MID,AND AFT ATTENDANTS SPEAKER AND CHIMES (continued) | | | | | | | | | | | | | | |
| 070 | 22 | | PA | | 5-2 | 23-42-11 | L01052 | | L1 | C | | | | SM00055 | | S | | 277-278 |
| 071 | 22 | | PA | | 35-1 | 33-25-11 | SP03992 | | | S | | | 3 | D05353J | | | | 050-099 |
| 071 | 20 | | PA | | 10-0 | 23-42-11 | L01052 | | 3 | C | | | | GD04198 | D.. | 2 | | 275-276 |
| 071 | 20 | | PA | | 4-11 | 23-42-11 | L01052 | | 3 | C | | | | GD04198 | D.. | 2 | | 277-278 |
| 077 | 24 | | PK | | 139-1 | 23-34-13 | D05353J | | 2 | | | | | D04647J | | 14 | | 050-099 |
| 082 | 24 | | PK | | 41-5 | 23-34-13 | D05327J | | 2 | | | | | SM00024 | | 9 | | 155 |
| 087 | 24 | | PK | | 68-5 | 33-25-11 | SP03702 | | | 9 | | | | B00139 | CAP | Y | | 150, 153-199 |
| 087 | 24 | | PK | | 68-5 | 33-25-11 | SP03702 | | | 9 | | | | B00139 | HI | C | | 151-152 |
| 105 | 22 | | PA | | 11-8 | 23-42-11 | D04397J | | 1 | | | | | SM00002 | | S | | 050-099 |
| 105 | 22 | | PA | | 17-8 | 23-42-11 | SM00002 | | | S | | | | D04397J | | 1 | | 150-199 |
| 107 | 22 | | PA | | 15-5 | 33-25-11 | SP03700 | | | S | | | | D04397J | | 3 | | 050-099 |
| 107 | 22 | | PA | | 15-10 | 33-25-11 | SP03700 | | | S | | | | D04397J | | 3 | | 150-199 |
| 108 | 20 | | PA | | 7-8 | 23-42-11 | GD01236 | | D.. | 2 | | | | D04397J | | 4 | | 050-099 |
| 108 | 20 | | PA | | 8-3 | 23-42-11 | GD01236 | | D.. | 2 | | | | D04397J | | 4 | | 150-199 |
| 129 | 22 | | PA | | 29-3 | 23-34-13 | D04647J | | | 6 | | | | SM00044 | | S | | 050-099 |
| 129 | 24 | | PK | | 38-10 | 23-34-13 | D04647J | | | 6 | | | | SM00044 | | S | | 150-199 |
| 129 | 24 | | PK | | 44-3 | 23-34-13 | D04647J | | | 6 | | | | D05329J | | 2 | | 275-299 |
| 130 | 24 | | PK | | 29-3 | 23-34-13 | SM00039 | | | S | | | | D04647J | | 7 | | 050-099 |
| 130 | 24 | | PK | | 42-1 | 23-34-13 | D04647J | | | 7 | | | | D05327J | | 2 | | 150-154, 156-157, 275-299 |
| 130 | 24 | | PK | | 1-2 | 23-34-13 | D04647J | | | 7 | | | | SM00024 | | 9 | | 155 |
| 130 | 24 | | PK | | 43-1 | 23-34-13 | D04647J | | | 7 | | | | L00579 | L3 | C | | 162-199 |
| 131 | 24 | | PK | | 80-10 | 23-34-13 | D04647J | | | 21 | | | | D06055J | | 2 | | 050-099 |
| 131 | 24 | | PK | | 57-2 | 23-34-13 | D04647J | | | 21 | | | | SM00038 | | S | | 150-154, 156-199 |
| 131 | 24 | | PK | | 57-2 | 23-34-13 | D04647J | | | 21 | | | | SM00038 | | 9 | | 155 |
| 131 | 24 | | PK | | 75-4 | 23-34-13 | D04647J | | | 21 | | | | SM00034 | | S | | 275-278 |
| 131 | 24 | | PK | | 71-11 | 23-34-13 | D04647J | | | 21 | | | | SM00034 | | S | | 280-299 |
| 132 | 24 | | PK | | 83-2 | 23-34-13 | D04647J | | | 22 | | | | D06057J | | 2 | | 050-099 |
| 132 | 24 | | PK | | 57-2 | 23-34-13 | SM00039 | | | S | | | | D04647J | | 22 | | 150-154, 156-199 |
| 132 | 24 | | PK | | 90-11 | 23-34-13 | L00581 | | L3 | C | | | | D04647J | | 22 | | 155 |
| 132 | 24 | | PK | | 75-4 | 23-34-13 | D04647J | | | 22 | | | | SM00033 | | S | | 275-278 |
| 132 | 24 | | PK | | 71-11 | 23-34-13 | D04647J | | | 22 | | | | SM00033 | | S | | 280-299 |
| 145 | 24 | | PK | | 22-2 | 23-34-13 | L00685 | | L3 | C | | | | SM00033 | | S | | 275-276 |
| 145 | 24 | | PK | | 12-4 | 23-34-13 | L00685 | | L3 | C | | | | SM00033 | | S | | 277-278 |
| 145 | 24 | | PK | | 15-10 | 23-34-13 | L00687 | | L3 | C | | | | SM00033 | | S | | 280-299 |
| 146 | 24 | | PK | | 19-4 | 23-34-13 | L00686 | | L3 | C | | | | SM00034 | | S | | 275-276 |
| 146 | 24 | | PK | | 9-0 | 23-34-13 | L00686 | | L3 | C | | | | SM00034 | | S | | 277-278 |
| 146 | 24 | | PK | | 12-6 | 23-34-13 | L00688 | | L3 | C | | | | SM00034 | | S | | 280-299 |
| 156 | 22 | | PA | | 25-8 | 23-42-11 | SM00035 | | | S | | | | SM00002 | | S | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 12

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0665 | 286T0665 | | | E2-5 TO FWD,MID,AND AFT ATTENDANTS SPEAKER AND CHIMES (continued) | | | | | | | | | | | |
| 156 | 22 | | PA | | 28-2 | 23-42-11 | SM00035 | | S | | SM00002 | | S | | 150-199 |
| 157 | 20 | | PA | | 4-5 | 23-42-11 | GD01930 | D.. | 2 | | D06051J | 4 | | | 050-099 |
| 157 | 20 | | PA | | 4-2 | 23-42-11 | GD01930 | D.. | 2 | | D06051J | 4 | | | 150-199 |
| 159 | 22 | | PA | | 13-5 | 23-42-11 | SM00035 | | S | | D06051J | 1 | | | 050-099 |
| 159 | 22 | | PA | | 1-10 | 23-42-11 | SM00035 | | S | | D06051J | 1 | | | 150-199 |
| 160 | 22 | | PA | | 15-4 | 23-42-11 | SM00035 | | S | | D06053J | 1 | | | 050-099 |
| 160 | 22 | | PA | | 2-11 | 23-42-11 | SM00035 | | S | | D06053J | 1 | | | 150-199 |
| 161 | 20 | | PA | | 1-5 | 23-42-11 | GD01930 | D.. | 2 | | D06053J | 4 | | | 050-099, 150-199 |
| 162 | 20 | | PA | | 1-10 | 23-42-11 | GD01756 | D.. | 2 | | D06059J | 4 | | | 050-099 |
| 162 | 20 | | PA | | 1-9 | 23-42-11 | GD04906 | D.. | 2 | | D06059J | 4 | | | 150-199 |
| 163 | 22 | | PA | | 3-9 | 23-42-11 | SM00050 | | S | | D06059J | 1 | | | 050-099 |
| 163 | 22 | | PA | | 9-3 | 23-42-11 | SM00001 | | S | | D06059J | 1 | | | 150-199 |
| 164 | 22 | | PA | | 1-11 | 23-42-11 | SM00050 | | S | | D06061J | 1 | | | 050-099 |
| 164 | 22 | | PA | | 7-4 | 23-42-11 | SM00001 | | S | | D06061J | 1 | | | 150-199 |
| 165 | 20 | | PA | | 4-2 | 23-42-11 | GD01756 | D.. | 2 | | D06061J | 4 | | | 050-099 |
| 165 | 20 | | PA | | 3-9 | 23-42-11 | GD04906 | D.. | 2 | | D06061J | 4 | | | 150-199 |
| 167 | 22 | | PA | | 12-2 | 23-42-11 | SM00002 | | S | | D06033J | 1 | | | 050-099 |
| 167 | 22 | | PA | | 7-2 | 23-42-11 | SM00002 | | S | | D06033J | 1 | | | 150-199 |
| 170 | 24 | | PK | | 30-4 | 23-34-13 | SM00039 | | S | | D06053J | 2 | | | 050-099 |
| 170 | 24 | | PK | | 2-11 | 23-34-13 | SM00039 | | S | | D06053J | 2 | | | 150-154, 156-199 |
| 170 | 24 | | PK | | 58-11 | 23-34-13 | SM00024 | | 9 | | D06053J | 2 | | | 155 |
| 171 | 24 | | PK | | 14-4 | 23-34-13 | SM00039 | | S | | L00579 | L3 | C | | 050-099 |
| 171 | 24 | | PK | | 43-9 | 23-34-13 | SM00039 | | S | | D06057J | 2 | | | 150-154, 156, 162-199 |
| 171 | 24 | | PK | | 45-10 | 23-34-13 | SM00039 | | S | | L00581 | L3 | C | | 157 |
| 172 | 24 | | PK | | 41-5 | 23-34-13 | SM00038 | | S | | D06055J | 2 | | | 150-154, 156, 162-199 |
| 172 | 24 | | PK | | 42-11 | 23-34-13 | L00582 | L3 | C | | SM00038 | | 9 | | 155 |
| 172 | 24 | | PK | | 42-11 | 23-34-13 | SM00038 | | S | | L00582 | L3 | C | | 157 |
| 173 | 24 | | PK | | 7-7 | 23-34-13 | SM00047 | | S | | D06051J | 2 | | | 050-099 |
| 173 | 24 | | PK | | 1-10 | 23-34-13 | SM00038 | | S | | D06051J | 2 | | | 150-154, 156-199 |
| 173 | 24 | | PK | | 36-2 | 23-34-13 | SM00044 | | S | | D06051J | 2 | | | 155 |
| 174 | 24 | | PK | | 41-4 | 23-42-12 | B00376 | | H/L | C | SM00018 | | S | | 150-199 |
| 175 | 22 | | PA | | 41-4 | 23-42-12 | B00376 | | 28V | C | SM00015 | | S | | 150-199 |
| 176 | 20 | | PA | | 19-5 | 23-42-12 | B00376 | | GND | C | GD06733 | D.. | 2 | | 150-199 |
| 177 | 24 | | PK | | 25-5 | 23-34-13 | SM00047 | | S | | D05331J | 12 | | | 050-099 |
| 177 | 24 | | PK | | 49-11 | 23-34-13 | SM00004 | | S | | D06482J | 24 | | | 150-199 |
| 178 | 24 | | PK | | 47-6 | 23-34-13 | SM00039 | | S | | D05331J | 11 | | | 050-099 |
| 178 | 24 | | PK | | 49-11 | 23-34-13 | SM00005 | | S | | D06482J | 23 | | | 150-199 |
| 179 | 22 | | PA | | 16-10 | 33-25-11 | D06482J | | 6 | | SP03696 | | 9 | | 150-199 |
| 180 | 22 | | PA | | 16-10 | 33-25-11 | D06482J | | 5 | | SP00570 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 13

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|--------|---------|-------------|------|------|-----------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type | Splice |
| W0665 | 286T0665 | | | E2-5 TO FWD,MID,AND AFT ATTENDANTS SPEAKER AND CHIMES (continued) | | | | | | | | | | | | |
| 181 | 22 | | PA | | 33-6 | 33-25-11 | SP00570 | | | S | | D06051J | 3 | | | 050-099 |
| 181 | 22 | | PA | | 100-3 | 33-25-11 | D06051J | | 3 | | | SP00576 | | S | | 150-199 |
| 183 | 22 | | PA | | 21-2 | 23-42-12 | SM00016 | | | S | | D07090P | 12 | | | 280-299 |
| 184 | 20 | | PA | | 6-8 | 23-42-12 | D07090P | | 10 | | | GD04874 | D.. | 2 | | 280-299 |
| 185 | 24 | | PK | | 21-2 | 23-42-12 | D07090P | | 11 | | | SM00019 | | S | | 280-299 |
| 190 | 22 | | PA | | 43-9 | 33-25-11 | SP00568 | | | S | | D06053J | 3 | | | 050-099 |
| 190 | 22 | | PA | | 44-1 | 33-25-11 | SP00568 | | | S | | D06053J | 3 | | | 150-199 |
| 191 | 22 | | PA | | 14-4 | 33-25-11 | SP00570 | | | S | | D06055J | 3 | | | 050-099 |
| 191 | 22 | | PA | | 71-5 | 33-25-11 | SP00576 | | | S | | D06055J | 3 | | | 150-154, 156, 162-199 |
| 191 | 22 | | PA | | 16-1 | 33-25-11 | SP03696 | | | 9 | | L01230 | L2 | C | | 155, 157 |
| 191 | 22 | | PA | | 10-4 | 33-25-11 | SM00056 | | | S | | D06055J | 3 | | | 277-299 |
| 194 | 22 | | PA | | 9-0 | 23-42-11 | SM00048 | | | S | | L01055 | L1 | C | | 280-299 |
| 195 | 20 | | PA | | 7-2 | 23-42-11 | GD04198 | | D.. | 2 | | L01055 | 3 | C | | 280-299 |
| 196 | 22 | | PA | | 12-4 | 23-42-11 | SM00049 | | | S | | L01052 | L1 | C | | 280-299 |
| 197 | 20 | | PA | | 4-11 | 23-42-11 | GD04198 | | D.. | 2 | | L01052 | 3 | C | | 280-299 |
| 198 | 24 | | PK | | 66-1 | 33-25-11 | SP03702 | | | 9 | | B00376 | HI | C | | 150-199 |
| 199 | 22 | | PA | | 16-8 | 33-25-11 | SP00572 | | | S | | D06057J | 3 | | | 050-099 |
| 199 | 22 | | PA | | 19-7 | 33-25-11 | SP00574 | | | S | | D06057J | 3 | | | 150-154, 156, 162-199 |
| 199 | 22 | | PA | | 21-8 | 33-25-11 | SP00574 | | | S | | L01229 | L2 | C | | 155, 157 |
| 199 | 22 | | PA | | 12-3 | 33-25-11 | SM00057 | | | S | | D06057J | 3 | | | 277-299 |
| 201B | 22 | | PB | IA | 7-6 | 23-31-14 | D04647J | | 2 | | | SM00006 | | S | | 050-099 |
| 201R | 22 | | PB | IA | 0-0 | 23-31-14 | D04647J | | 1 | | | SM00007 | | S | | 050-099 |
| 202B | 22 | | PB | IB | 40-4 | 23-31-14 | SM00008 | | | S | | B00072 | - | X | | 050-099 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-14 | SM00007 | | | S | | B00072 | + | X | | 050-099 |
| 203B | 22 | | PB | IC | 39-3 | 23-31-14 | SM00006 | | | S | | B00073 | - | X | | 050-099 |
| 203R | 22 | | PB | IC | 0-0 | 23-31-14 | SM00008 | | | S | | B00073 | + | X | | 050-099 |
| 204B | 22 | | PB | ID | 69-9 | 23-31-14 | SM00006 | | | S | | SM00009 | | S | | 050-099 |
| 204R | 22 | | PB | ID | 0-0 | 23-31-14 | SM00007 | | | S | | SM00010 | | S | | 050-099 |
| 206B | 22 | | PB | IF | 0-7 | 23-31-14 | SM00009 | | | S | | D05331J | 7 | | | 050-099 |
| 206B | 22 | | PB | IF | 24-10 | 23-31-14 | SP03592 | | | S | | D06482J | 8 | | | 150-199 |
| 206B | 22 | | PB | IF | 15-0 | 23-31-14 | SP01694 | | | S | | D05331J | 8 | | | 275-278 |
| 206B | 22 | | PB | IF | 15-3 | 23-31-14 | D05331J | | 8 | | | SM00042 | | S | | 280-299 |
| 206R | 22 | | PB | IF | 0-0 | 23-31-14 | SM00010 | | | S | | D05331J | 8 | | | 050-099 |
| 206R | 22 | | PB | IF | 0-0 | 23-31-14 | SP03590 | | | S | | D06482J | 7 | | | 150-199 |
| 206R | 22 | | PB | IF | 0-0 | 23-31-14 | SP01692 | | | S | | D05331J | 7 | | | 275-278 |
| 206R | 22 | | PB | IF | 0-0 | 23-31-14 | D05331J | | 7 | | | SM00041 | | S | | 280-299 |
| 207B | 22 | | PB | IG | 72-2 | 23-31-14 | SM00009 | | | S | | SM00012 | | S | | 050-099 |
| 207R | 22 | | PB | IG | 0-0 | 23-31-14 | SM00010 | | | S | | SM00013 | | S | | 050-099 |
| 208B | 22 | | PB | IH | 8-11 | 23-31-14 | SM00014 | | | S | | B00076 | - | X | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 14

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0665 | 286T0665 | | | E2-5 TO FWD,MID,AND AFT ATTENDANTS SPEAKER AND CHIMES (continued) | | | | | | | | | | | |
| 208R | 22 | PB | IH | | 0-0 | 23-31-14 | SM00013 | | S | | B00076 | + | X | | 050-099 |
| 209B | 22 | PB | II | | 2-10 | 23-31-14 | SM00012 | | S | | B00077 | - | X | | 050-099 |
| 209R | 22 | PB | II | | 0-0 | 23-31-14 | SM00014 | | S | | B00077 | + | X | | 050-099 |
| 212B | 22 | PB | IL | | 29-8 | 23-31-14 | SP01698 | | S | | SM00028 | | S | | 050-099 |
| 212B | 22 | PB | IL | | 23-1 | 23-31-14 | SP01698 | | S | | SM00030 | | S | | 150-199, 275-299 |
| 212R | 22 | PB | IL | | 0-0 | 23-31-14 | SP01696 | | S | | SM00027 | | S | | 050-099 |
| 212R | 22 | PB | IL | | 0-0 | 23-31-14 | SP01696 | | S | | SM00029 | | S | | 150-199, 275-299 |
| 213B | 22 | PB | IM | | 6-7 | 23-31-14 | SM00028 | | S | | B00229 | COM | Z | | 050-099 |
| 213B | 22 | PB | IM | | 4-8 | 23-31-14 | SM00028 | | S | | B00229 | COM | Z | | 150-199, 275-299 |
| 213R | 22 | PB | IM | | 0-0 | 23-31-14 | SM00027 | | S | | B00229 | 1K | Z | | ALL |
| 214B | 22 | PB | IN | | 10-0 | 23-31-14 | SM00028 | | S | | B00230 | COM | Z | | 050-099 |
| 214B | 22 | PB | IN | | 8-4 | 23-31-14 | SM00028 | | S | | B00230 | COM | Z | | 150-199, 275-299 |
| 214R | 22 | PB | IN | | 0-0 | 23-31-14 | SM00027 | | S | | B00230 | 1K | Z | | ALL |
| 215B | 22 | PB | IO | | 8-8 | 23-31-14 | SM00028 | | S | | SM00030 | | S | | 150-199, 275-299 |
| 215R | 22 | PB | IO | | 0-0 | 23-31-14 | SM00027 | | S | | SM00029 | | S | | 150-199, 275-299 |
| 216B | 22 | PB | IP | | 11-10 | 23-31-14 | B00235 | COM | Z | | SM00030 | | S | | 150-199 |
| 216B | 22 | PB | IP | | 9-1 | 23-31-14 | B00235 | COM | Z | | SM00030 | | S | | 275-299 |
| 216R | 22 | PB | IP | | 0-0 | 23-31-14 | B00235 | 4K | Z | | SM00029 | | S | | 150-199, 275-299 |
| 217B | 22 | PB | IQ | | 7-2 | 23-31-14 | B00236 | COM | Z | | SM00030 | | S | | 280-299 |
| 217R | 22 | PB | IQ | | 0-0 | 23-31-14 | B00236 | 4K | Z | | SM00029 | | S | | 280-299 |
| 219B | 22 | PB | IS | | 8-4 | 23-31-14 | SP01694 | | S | | SM00042 | | S | | 280-299 |
| 219R | 22 | PB | IS | | 0-0 | 23-31-14 | SP01692 | | S | | SM00041 | | S | | 280-299 |
| 220B | 22 | PB | IT | | 19-3 | 23-31-14 | D07090P | 8 | | | SM00042 | | S | | 280-299 |
| 220R | 22 | PB | IT | | 0-0 | 23-31-14 | D07090P | 7 | | | SM00041 | | S | | 280-299 |
| 227B | 22 | PB | JB | | 18-1 | 23-31-14 | D07092J | 2 | | | SM00030 | | S | | 280-299 |
| 227R | 22 | PB | JB | | 0-0 | 23-31-14 | D07092J | 1 | | | SM00029 | | S | | 280-299 |
| 503 | 22 | PA | | | 60-11 | 23-42-11 | SM00050 | | S | | SM00003 | | S | | 050-099 |
| 504 | 24 | PK | | | 23-1 | 23-34-13 | SM00047 | | S | | SM00044 | | S | | 050-099 |
| 505 | 22 | PA | | | 37-0 | 23-42-11 | D04647J | 25 | | | D06033J | 2 | | | 050-099 |
| 505 | 22 | PA | | | 35-8 | 23-42-11 | D04647J | 25 | | | D06033J | 2 | | | 162-199 |
| 506 | 22 | PA | | | 37-0 | 23-42-11 | D04647J | 26 | | | D06033J | 3 | | | 050-099 |
| 506 | 22 | PA | | | 35-8 | 23-42-11 | D04647J | 26 | | | D06033J | 3 | | | 162-199 |
| 507 | 22 | PA | | | 37-0 | 23-42-11 | D04647J | 27 | | | D06033J | 4 | | | 050-099 |
| 507 | 22 | PA | | | 35-8 | 23-42-11 | D04647J | 27 | | | D06033J | 4 | | | 162-199 |
| 508 | 22 | PA | | | 37-0 | 23-42-11 | D04647J | 28 | | | D06033J | 5 | | | 050-099 |
| 508 | 22 | PA | | | 35-8 | 23-42-11 | D04647J | 28 | | | D06033J | 5 | | | 162-199 |
| 511 | 22 | PA | | | 15-0 | 33-25-11 | SP00570 | | S | | L01229 | L2 | C | | 275-276 |
| 511 | 22 | PA | | | 14-9 | 33-25-11 | SM00057 | | S | | L01229 | L2 | C | | 277-299 |
| 512 | 22 | PA | | | 25-0 | 33-25-11 | SP03214 | | S | | L01230 | L2 | C | | 275-276 |

WIRE LIST
D280T132

91-21-11
Section W0660
Page 15
Mar 14/2007



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0665 | 286T0665 | E2-5 TO FWD,MID,AND AFT ATTENDANTS SPEAKER AND CHIMES (continued) | | | | | | | | | | | | | | |
| 512 | 22 | PA | | 11-5 | 33-25-11 | SM00056 | | S | | L01230 | L2 | C | | 277-299 | | |
| 521 | 22 | PA | | 8-3 | 23-42-11 | SM00003 | | S | | D07090P | 1 | | | 280-299 | | |
| 522 | 20 | PA | | 6-8 | 23-42-11 | GD04874 | D.. | 2 | | D07090P | 4 | | | 280-299 | | |
| 523 | 22 | PA | | 10-0 | 23-42-11 | D05331J | | 1 | | SM00055 | | S | | 275-276 | | |
| 523 | 22 | PA | | 2-9 | 23-42-11 | D05331J | | 1 | | SM00055 | | S | | 277-278 | | |
| 524 | 24 | PK | | 21-2 | 23-34-13 | D07090P | | 2 | | SM00034 | | S | | 280-299 | | |
| 525 | 24 | PK | | 21-2 | 23-34-13 | D07090P | | 3 | | SM00033 | | S | | 280-299 | | |
| 526 | 22 | PA | | 28-4 | SPARE | SM00056 | | S | | D07090P | 6 | | | 280-299 | | |
| 527 | 22 | PA | | 10-0 | 33-25-11 | SM00056 | | S | | SP03214 | | S | | 277-299 | | |
| 528 | 22 | PA | | 10-0 | 33-25-11 | SM00057 | | S | | SP00570 | | S | | 277-299 | | |
| 529 | 22 | PA | | 28-4 | SPARE | SM00057 | | S | | D07090P | 5 | | | 280-299 | | |
| 603 | 22 | PA | | 18-3 | 23-42-11 | SM00048 | | S | | SM00003 | | S | | 280-299 | | |
| 604 | 22 | PA | | 18-3 | 23-42-11 | SM00049 | | S | | SM00003 | | S | | 280-299 | | |
| W0666 | 286T0666 | FWD AND AFT CARGO HANDLING POWER | | | | | | | | | | | | | | |
| 001 | 08 | PA | | 6-0 | 25-53-11 | C00350 | A1 | D | | SM00001 | | GE | | ALL | | |
| 002 | 08 | PA | | 6-0 | 25-53-11 | C00350 | B1 | D | | SM00002 | | GE | | ALL | | |
| 003 | 08 | PA | | 6-0 | 25-53-11 | C00350 | C1 | D | | SM00003 | | GE | | ALL | | |
| 004 | 06 | QY | | 23-0 | 25-53-11 | SM00001 | | GE | | SM00004 | | GE | | 050-099 | | |
| 004 | 06 | QY | | 20-0 | 25-53-11 | SM00001 | | GE | | SM00004 | | GE | | 150-199, 275-299 | | |
| 005 | 06 | QY | | 23-0 | 25-53-11 | SM00002 | | GE | | SM00005 | | GE | | 050-099 | | |
| 005 | 06 | QY | | 20-0 | 25-53-11 | SM00002 | | GE | | SM00005 | | GE | | 150-199, 275-299 | | |
| 006 | 06 | QY | | 23-0 | 25-53-11 | SM00003 | | GE | | SM00006 | | GE | | 050-099 | | |
| 006 | 06 | QY | | 20-0 | 25-53-11 | SM00003 | | GE | | SM00006 | | GE | | 150-199, 275-299 | | |
| 007 | 08 | PA | | 4-0 | 25-53-11 | SM00004 | | GE | | K00245 | A1 | E | | 050-099 | | |
| 007 | 08 | PA | | 3-0 | 25-53-11 | SM00004 | | GE | | K00245 | A1 | E | | 150-199, 275-278 | | |
| 007 | 08 | PA | | 5-0 | 25-53-11 | SM00004 | | GE | | K00245 | A1 | E | | 280-299 | | |
| 008 | 08 | PA | | 4-0 | 25-53-11 | SM00005 | | GE | | K00245 | B1 | E | | 050-099 | | |
| 008 | 08 | PA | | 3-0 | 25-53-11 | SM00005 | | GE | | K00245 | B1 | E | | 150-199, 275-278 | | |
| 008 | 08 | PA | | 5-0 | 25-53-11 | SM00005 | | GE | | K00245 | B1 | E | | 280-299 | | |
| 009 | 08 | PA | | 4-0 | 25-53-11 | SM00006 | | GE | | K00245 | C1 | E | | 050-099 | | |
| 009 | 08 | PA | | 3-0 | 25-53-11 | SM00006 | | GE | | K00245 | C1 | E | | 150-199, 275-278 | | |
| 009 | 08 | PA | | 5-0 | 25-53-11 | SM00006 | | GE | | K00245 | C1 | E | | 280-299 | | |
| 011 | 08 | PA | | 6-0 | 25-53-21 | C00351 | A1 | D | | SM00007 | | GE | | 050-099 | | |
| 011 | 08 | PA | | 7-0 | 25-53-21 | C00351 | A1 | D | | SM00007 | | GE | | 150-199, 275-299 | | |
| 012 | 08 | PA | | 6-0 | 25-53-21 | C00351 | B1 | D | | SM00008 | | GE | | 050-099 | | |
| 012 | 08 | PA | | 7-0 | 25-53-21 | C00351 | B1 | D | | SM00008 | | GE | | 150-199, 275-299 | | |
| 013 | 08 | PA | | 6-0 | 25-53-21 | C00351 | C1 | D | | SM00009 | | GE | | 050-099 | | |
| 013 | 08 | PA | | 7-0 | 25-53-21 | C00351 | C1 | D | | SM00009 | | GE | | 150-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 16

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0666 | 286T0666 | | | FWD AND AFT CARGO HANDLING POWER (continued) | | | | | | | | | | | |
| 014 | 06 | | QY | | 89-0 | 25-53-21 | SM00007 | | GE | | SM00010 | | GE | | 050-099 |
| 014 | 06 | | QY | | 109-0 | 25-53-21 | SM00007 | | GE | | SM00010 | | GE | | 150-199, 275-278 |
| 014 | 06 | | QY | | 108-0 | 25-53-21 | SM00007 | | GE | | SM00010 | | GE | | 280-299 |
| 015 | 06 | | QY | | 89-0 | 25-53-21 | SM00008 | | GE | | SM00011 | | GE | | 050-099 |
| 015 | 06 | | QY | | 109-0 | 25-53-21 | SM00008 | | GE | | SM00011 | | GE | | 150-199, 275-278 |
| 015 | 06 | | QY | | 108-0 | 25-53-21 | SM00008 | | GE | | SM00011 | | GE | | 280-299 |
| 016 | 06 | | QY | | 89-0 | 25-53-21 | SM00009 | | GE | | SM00012 | | GE | | 050-099 |
| 016 | 06 | | QY | | 109-0 | 25-53-21 | SM00009 | | GE | | SM00012 | | GE | | 150-199, 275-278 |
| 016 | 06 | | QY | | 108-0 | 25-53-21 | SM00009 | | GE | | SM00012 | | GE | | 280-299 |
| 017 | 08 | | PA | | 5-0 | 25-53-21 | SM00010 | | GE | | K00278 | A1 | E | | ALL |
| 018 | 08 | | PA | | 5-0 | 25-53-21 | SM00011 | | GE | | K00278 | B1 | E | | ALL |
| 019 | 08 | | PA | | 5-0 | 25-53-21 | SM00012 | | GE | | K00278 | C1 | E | | ALL |
| W0668 | 286T0668 | | | MAIN LANDING GEAR (LOWER) LEFT - BRAKE TEMP , TPIS | | | | | | | | | | | |
| 201B | 20 | 8K | B | | 20-0 | 32-42-11 | D05022P | 2 | | | D02016 | 3 | | | ALL |
| 201R | 20 | 8K | B | | 0-0 | 32-42-11 | D05022P | 1 | | | D02016 | 1 | | | ALL |
| 201Z | | | B | | 0-0 | 32-42-11 | D05022P | 3 | | | D02016 | DED | | | ALL |
| 202B | 20 | 8K | C | | 20-0 | 32-42-11 | D05022P | 13 | | | D02018 | 3 | | | ALL |
| 202R | 20 | 8K | C | | 0-0 | 32-42-11 | D05022P | 12 | | | D02018 | 1 | | | ALL |
| 202Z | | | C | | 0-0 | 32-42-11 | D05022P | 14 | | | D02018 | DED | | | ALL |
| 207B | 20 | VG | F | | 20-0 | 32-45-13 | D05022P | 25 | | | D13384 | 2 | | | 050-099, 155-156, 163-199, 275-299 |
| 207B | 20 | VG | F | | 20-0 | 32-45-13 | D05022P | 25 | | | D13384 | CAP | Y | | 157-162 |
| 207R | 20 | VG | F | | 0-0 | 32-45-13 | D05022P | 26 | | | D13384 | 1 | | | 050-099, 155-156, 163-199, 275-299 |
| 207R | 20 | VG | F | | 0-0 | 32-45-13 | D05022P | 26 | | | D13384 | CAP | Y | | 157-162 |
| 207Z | | | F | | 0-0 | 32-45-13 | D05022P | 27 | | | D13384 | 3 | | | 050-099, 155-156, 163-199, 275-299 |
| 207Z | | | F | | 0-0 | 32-45-13 | D05022P | 27 | | | D13384 | DED | | | 157-162 |
| 208B | 20 | VG | G | | 20-0 | 32-45-13 | D05022P | 28 | | | D13382 | 2 | | | 050-099, 155-156, 163-199, 275-299 |
| 208B | 20 | VG | G | | 20-0 | 32-45-13 | D05022P | 28 | | | D13382 | CAP | Y | | 157-162 |
| 208R | 20 | VG | G | | 0-0 | 32-45-13 | D05022P | 29 | | | D13382 | 1 | | | 050-099, 155-156, 163-199, 275-299 |
| 208R | 20 | VG | G | | 0-0 | 32-45-13 | D05022P | 29 | | | D13382 | CAP | Y | | 157-162 |
| 208Z | | | G | | 0-0 | 32-45-13 | D05022P | 30 | | | D13382 | 3 | | | 050-099, 155-156, 163-199, 275-299 |
| 208Z | | | G | | 0-0 | 32-45-13 | D05022P | 30 | | | D13382 | DED | | | 157-162 |
| 451G | 18 | UY | D | | 16-0 | 32-46-11 | D05022P | 8 | 4G | | D01714 | 3 | 4H | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 17

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|--|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0668 | 286T0668 | | | MAIN LANDING GEAR (LOWER) LEFT - BRAKE TEMP , TPIS (continued) | | | | | | | | | | | | |
| 451W | 18 | UY | D | 0-0 | 32-46-11 | D05022P | 7 | 4K | | D01714 | 1 | 4L | | ALL | | |
| 452G | 18 | UY | E | 16-0 | 32-46-11 | D05022P | 10 | 4G | | D01718 | 3 | 4H | | ALL | | |
| 452W | 18 | UY | E | 0-0 | 32-46-11 | D05022P | 9 | 4K | | D01718 | 1 | 4L | | ALL | | |
| A-A | | | A | 0-0 | 32-09-12 | D05022P | 5 | | | S00267 | | RED | | ALL | | |
| A-B | | | A | 0-0 | 32-09-12 | D05022P | 6 | | | S00267 | | BLU | | ALL | | |
| W0669 | 286T0669 | | | E2-3 TO LW BODY DISC (AIDS-LEFT ENGINE) | | | | | | | | | | | | |
| 003 | 22 | PA | | 61-0 | SPARE | D06300J | 25 | | | D05517J | 25 | | | 150-199, 275-299 | | |
| 203B | 22 | PR | A | 61-0 | SPARE | D06300J | 19 | | | D05517J | 19 | | | 150-199, 275-299 | | |
| 203R | 22 | PR | A | 0-0 | SPARE | D06300J | 18 | | | D05517J | 18 | | | 150-199, 275-299 | | |
| 203Z | | | A | 0-0 | SPARE | D06300J | 20 | | | D05517J | 20 | | | 150-199, 275-299 | | |
| 302B | 20 | PC | MB | 61-0 | SPARE | D05517J | 2 | | | D06300J | 2 | | | 150-199 | | |
| 302R | 20 | PC | MB | 0-0 | SPARE | D05517J | 1 | | | D06300J | 1 | | | 150-199 | | |
| 302Y | 20 | PC | MB | 0-0 | SPARE | D05517J | 3 | | | D06300J | 3 | | | 150-199 | | |
| 303B | 20 | PS | MC | 61-0 | SPARE | D05517J | 13 | | | D06300J | 13 | | | 150-199 | | |
| 303R | 20 | PS | MC | 0-0 | SPARE | D05517J | 5 | | | D06300J | 5 | | | 150-199 | | |
| 303Y | 20 | PS | MC | 0-0 | SPARE | D05517J | 14 | | | D06300J | 14 | | | 150-199 | | |
| 303Z | | | MC | 0-0 | SPARE | D05517J | 4 | | | D06300J | 4 | | | 150-199 | | |

WIRE LIST

D280T132

91-21-11

Section W0660

Page 18 End

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | | | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|---------|---------|--|--|----|----|--|--|-----|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | | | | | | |
| W0670 | 286T0670 | | | MAIN LANDING GEAR (UPPER) LEFT - BRAKE TEMP , TPIS | | | | | | | | | | | | | | | | | | | | | |
| 201B | 18 | | 8J | B | 9-0 | 32-61-11 | D05026J | | | | | | | | 2 | D01746J | | | | 2 | | | | ALL | |
| 201R | 18 | | 8J | B | 0-0 | 32-61-11 | D05026J | | | | | | | | 1 | D01746J | | | | 1 | | | | | ALL |
| 202B | 18 | | 8J | C | 9-0 | 32-61-11 | D05026J | | | | | | | | 4 | D01748J | | | | 2 | | | | | ALL |
| 202R | 18 | | 8J | C | 0-0 | 32-61-11 | D05026J | | | | | | | | 3 | D01748J | | | | 1 | | | | | ALL |
| 203B | 18 | | 8J | A | 9-0 | 32-09-11 | D05026J | | | | | | | | 6 | D05028J | | | | 6 | | | | | ALL |
| 203R | 18 | | 8J | A | 0-0 | 32-09-11 | D05026J | | | | | | | | 5 | D05028J | | | | 5 | | | | | ALL |
| 204B | 20 | | 8K | D | 9-0 | 32-42-11 | D05026J | | | | | | | | 12 | D05028J | | | | 2 | | | | | ALL |
| 204R | 20 | | 8K | D | 0-0 | 32-42-11 | D05026J | | | | | | | | 11 | D05028J | | | | 1 | | | | | ALL |
| 204Z | | | | D | 0-0 | 32-42-11 | D05026J | | | | | | | | 15 | D05028J | | | | 3 | | | | | ALL |
| 205B | 20 | | 8K | E | 9-0 | 32-42-11 | D05026J | | | | | | | | 14 | D05028J | | | | 13 | | | | | ALL |
| 205R | 20 | | 8K | E | 0-0 | 32-42-11 | D05026J | | | | | | | | 13 | D05028J | | | | 12 | | | | | ALL |
| 205Z | | | | E | 0-0 | 32-42-11 | D05026J | | | | | | | | 16 | D05028J | | | | 14 | | | | | ALL |
| 207B | 20 | | VG | H | 9-0 | 32-45-13 | D05026J | | | | | | | | 25 | D05028J | | | | 25 | | | | | 050-099, 155-199, 275-299 |
| 207R | 20 | | VG | H | 0-0 | 32-45-13 | D05026J | | | | | | | | 26 | D05028J | | | | 26 | | | | | 050-099, 155-199, 275-299 |
| 207Z | | | | H | 0-0 | 32-45-13 | D05026J | | | | | | | | 27 | D05028J | | | | 27 | | | | | 050-099, 155-199, 275-299 |
| 208B | 20 | | VG | J | 9-0 | 32-45-13 | D05026J | | | | | | | | 28 | D05028J | | | | 28 | | | | | 050-099, 155-199, 275-299 |
| 208R | 20 | | VG | J | 0-0 | 32-45-13 | D05026J | | | | | | | | 29 | D05028J | | | | 29 | | | | | 050-099, 155-199, 275-299 |
| 208Z | | | | J | 0-0 | 32-45-13 | D05026J | | | | | | | | 30 | D05028J | | | | 30 | | | | | 050-099, 155-199, 275-299 |
| 451G | 18 | | UY | F | 9-0 | 32-46-11 | D05026J | | | | | | | | 8 | 4G | D05028J | | | 8 | 4H | | | | ALL |
| 451W | 18 | | UY | F | 0-0 | 32-46-11 | D05026J | | | | | | | | 7 | 4K | D05028J | | | 7 | 4L | | | | ALL |
| 452G | 18 | | UY | G | 9-0 | 32-46-11 | D05026J | | | | | | | | 10 | 4G | D05028J | | | 10 | 4H | | | | ALL |
| 452W | 18 | | UY | G | 0-0 | 32-46-11 | D05026J | | | | | | | | 9 | 4K | D05028J | | | 9 | 4L | | | | ALL |
| W0671 | 286T0671 | | | E2-3 TO RW BODY DISC (AIDS-RIGHT ENGINE) | | | | | | | | | | | | | | | | | | | | | |
| 003 | 22 | | PA | | 53-8 | SPARE | D06298J | | | | | | | | 25 | | D05519J | | | 25 | | | | | 150-199, 275-299 |
| 203B | 22 | | PR | B | 53-8 | SPARE | D06298J | | | | | | | | 19 | | D05519J | | | 19 | | | | | 150-199, 275-299 |
| 203R | 22 | | PR | B | 0-0 | SPARE | D06298J | | | | | | | | 18 | | D05519J | | | 18 | | | | | 150-199, 275-299 |
| 203Z | | | | B | 0-0 | SPARE | D06298J | | | | | | | | 20 | | D05519J | | | 20 | | | | | 150-199, 275-299 |
| W0672 | 286T0672 | | | AFT CARGO COMPARTMENT SMOKE DET 2 | | | | | | | | | | | | | | | | | | | | | |
| 002R | 24 | | PP | | 2-0 | 26-16-11 | D01464 | | | | | | | | 4 | | D06946J | | | 2 | | | | | ALL |
| 004R | 20 | | PH | | 2-0 | 26-16-11 | D01464 | | | | | | | | 5 | | D06946J | | | 4 | | | | | ALL |
| 006R | 20 | | PH | | 2-0 | 26-16-11 | D01464 | | | | | | | | 9 | | D06946J | | | 6 | | | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0670
Page 1
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0672 | 286T0672 | | | AFT CARGO COMPARTMENT SMOKE DET 2 (continued) | | | | | | | | | | | | | |
| 008R | 20 | | PH | 2-0 | 26-16-11 | D01464 | | | | | | | D06946J | 8 | | | ALL |
| 010R | 24 | | PP | 2-0 | 26-16-11 | D01464 | | | | | | | D06946J | 10 | | | ALL |
| 012R | 24 | | PP | 2-0 | 26-16-11 | D01464 | | | | | | | D06946J | 12 | | | ALL |
| W0674 | 286T0674 | | | MAIN LANDING GEAR (UPPER) LEFT - BRAKE TEMP , TPIS | | | | | | | | | | | | | |
| 201B | 18 | 8J | A | 9-0 | 32-61-11 | D05024J | | | | | | | D01750J | 2 | | | ALL |
| 201R | 18 | 8J | A | 0-0 | 32-61-11 | D05024J | | | | | | | D01750J | 1 | | | ALL |
| 202B | 18 | 8J | B | 9-0 | 32-61-11 | D05024J | | | | | | | D01752J | 2 | | | ALL |
| 202R | 18 | 8J | B | 0-0 | 32-61-11 | D05024J | | | | | | | D01752J | 1 | | | ALL |
| 203B | 18 | 8J | C | 9-0 | 32-09-12 | D05024J | | | | | | | D05022J | 6 | | | ALL |
| 203R | 18 | 8J | C | 0-0 | 32-09-12 | D05024J | | | | | | | D05022J | 5 | | | ALL |
| 204B | 20 | 8K | D | 9-0 | 32-42-11 | D05024J | | | | | | | D05022J | 12 | | | ALL |
| 204R | 20 | 8K | D | 0-0 | 32-42-11 | D05024J | | | | | | | D05022J | 11 | | | ALL |
| 204Z | | | D | 0-0 | 32-42-11 | D05024J | | | | | | | D05022J | 15 | | | ALL |
| 205B | 20 | 8K | E | 9-0 | 32-42-11 | D05024J | | | | | | | D05022J | 14 | | | ALL |
| 205R | 20 | 8K | E | 0-0 | 32-42-11 | D05024J | | | | | | | D05022J | 13 | | | ALL |
| 205Z | | | E | 0-0 | 32-42-11 | D05024J | | | | | | | D05022J | 16 | | | ALL |
| 207B | 20 | VG | H | 9-0 | 32-45-13 | D05024J | | | | | | | D05022J | 25 | | | 050-099, 155-199, 275-299 |
| 207R | 20 | VG | H | 0-0 | 32-45-13 | D05024J | | | | | | | D05022J | 26 | | | 050-099, 155-199, 275-299 |
| 207Z | | | H | 0-0 | 32-45-13 | D05024J | | | | | | | D05022J | 27 | | | 050-099, 155-199, 275-299 |
| 208B | 20 | VG | J | 9-0 | 32-45-13 | D05024J | | | | | | | D05022J | 28 | | | 050-099, 155-199, 275-299 |
| 208R | 20 | VG | J | 0-0 | 32-45-13 | D05024J | | | | | | | D05022J | 29 | | | 050-099, 155-199, 275-299 |
| 208Z | | | J | 0-0 | 32-45-13 | D05024J | | | | | | | D05022J | 30 | | | 050-099, 155-199, 275-299 |
| 451G | 18 | UY | F | 9-0 | 32-46-11 | D05024J | | | | | | | D05022J | 8 | 4G | | ALL |
| 451W | 18 | UY | F | 0-0 | 32-46-11 | D05024J | | | | | | | D05022J | 7 | 4K | | ALL |
| 452G | 18 | UY | G | 9-0 | 32-46-11 | D05024J | | | | | | | D05022J | 10 | 4G | | ALL |
| 452W | 18 | UY | G | 0-0 | 32-46-11 | D05024J | | | | | | | D05022J | 9 | 4K | | ALL |
| W0675 | 286T0675 | | | HF R,SHELF TO CONTROL PANEL | | | | | | | | | | | | | |
| 001 | 20 | | PA | 8-0 | 33-13-16 | D00737 | | | | | | | TB0064G | 1 | 2 | | ALL |
| 002 | 20 | | PA | 7-0 | 33-13-16 | D00737 | | | | | | | GD00267 | A.. | 2 | | ALL |
| 003 | 22 | | PA | 35-0 | 23-11-21 | D00737 | | | | | | | D04657J | 3 | | | ALL |
| 004 | 20 | | PA | 7-0 | 23-11-21 | D00737 | | | | | | | GD00267 | A.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0670

Page 2

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0675 | 286T0675 | | | HF R,SHELF TO CONTROL PANEL (continued) | | | | | | | | | | | |
| 005 | 24 | | PK | | 35-0 | 23-11-21 | D00737 | | | | D04657J | 5 | | | ALL |
| 006 | 20 | | PA | | 8-0 | 33-13-16 | D02695 | | | | TB0068H | 3 | 2 | | 156-157, 166-199, 277-299 |
| 009 | 20 | | PA | | 7-0 | 33-13-16 | D02695 | | | | GD00267 | A.. | 2 | | 156-157, 166-199, 277-299 |
| 010 | 20 | | PA | | 7-0 | 33-16-17 | D02695 | | | | TB0070Y | A031 | BJ | | 156-157, 166-199 |
| 010 | 20 | | PA | | 7-0 | 33-16-17 | D02695 | | | | TB0070Y | A031 | % | | 277-299 |
| 011 | 20 | | PA | | 7-0 | 33-16-17 | D02695 | | | | TB0070Z | 34 | BJ | | 156-157, 166-199 |
| 011 | 20 | | PA | | 7-0 | 33-16-17 | D02695 | | | | TB0070Z | 34 | % | | 277-299 |
| 012 | 24 | | PK | | 35-0 | 23-25-14 | D02695 | | | | D04657J | 1 | | | 156-157, 166-199, 277-278 |
| 013 | 24 | | PK | | 35-0 | 23-11-21 | D00737 | | | | D04657J | 4 | | | ALL |
| 014 | 24 | | PK | | 35-0 | 23-11-21 | D00737 | | | | D04657J | 6 | | | ALL |
| 016 | 24 | | PK | | 35-0 | 23-25-14 | D02695 | | | | D04657J | 2 | | | 156-157, 166-199, 277-278 |
| 017 | 24 | | PK | | 35-0 | 23-25-14 | D02695 | | | | D04657J | 12 | | | 156-157, 166-199, 277-278 |
| 018 | 24 | | PV | AR | 8-0 | 23-25-14 | D02695 | | | | TB0064F | A011 | 2 | | 156-157, 166-199, 277-278 |
| 018Z | | | | AR | 0-0 | 23-25-14 | D02695 | | DED | | TB0064F | DED | | | 156-157, 166-199, 277-278 |
| 019 | 24 | | PV | AS | 8-0 | 23-25-14 | D02695 | | 6 | | TB0064F | C011 | 2 | | 156-157, 166-199, 277-278 |
| 019Z | | | | AS | 0-0 | 23-25-14 | D02695 | | DED | | TB0064F | DED | | | 156-157, 166-199, 277-278 |
| 020 | 24 | | PV | AT | 8-0 | 23-25-14 | D02695 | | 14 | | TB0064F | A016 | 2 | | 156-157, 166-199, 277-278 |
| 020Z | | | | AT | 0-0 | 23-25-14 | D02695 | | DED | | TB0064F | DED | | | 156-157, 166-199, 277-278 |
| 021 | 20 | | PA | | 7-0 | 23-25-14 | D02695 | | 13 | | GD00267 | D.. | 2 | | 156-157, 166-199, 277-278 |
| 201 | 20 | | UA | | 1-6 | 23-11-21 | D00737 | | | FA | GD00629 | S.. | E | | ALL |
| 201B | 24 | | PW | IA | 35-0 | 23-11-21 | D00737 | | 10 | | D04657J | 10 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 23-11-21 | D00737 | | 9 | | D04657J | 9 | | | ALL |
| 201Z | | | | IA | 0-0 | 23-11-21 | D00737 | | | FA | D04657J | 11 | | | ALL |
| FRA | | | | | 0-0 | 23-11-21 | D00737 | | 11 | | D00737 | | | FA | ALL |
| FRB | | | | | 0-0 | 23-11-21 | D00737 | | 15 | | D00737 | | | FA | ALL |

WIRE LIST
D280T132

91-21-11
Section W0670
Page 3
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0676 | 286T0676 | | | MAIN LANDING GEAR (LOWER) LEFT - BRAKE TEMP , TPIS | | | | | | | | | | | | |
| 201B | 20 | 8K | A | 18-0 | 32-42-11 | D05028P | | 2 | | | D02012 | | 3 | | ALL | |
| 201R | 20 | 8K | A | 0-0 | 32-42-11 | D05028P | | 1 | | | D02012 | | 1 | | ALL | |
| 201Z | | | A | 0-0 | 32-42-11 | D05028P | | 3 | | | D02012 | DED | | | ALL | |
| 202B | 20 | 8K | B | 18-0 | 32-42-11 | D05028P | | 13 | | | D02014 | | 3 | | ALL | |
| 202R | 20 | 8K | B | 0-0 | 32-42-11 | D05028P | | 12 | | | D02014 | | 1 | | ALL | |
| 202Z | | | B | 0-0 | 32-42-11 | D05028P | | 14 | | | D02014 | DED | | | ALL | |
| 207B | 20 | VG | F | 20-0 | 32-45-13 | D05028P | | 25 | | | D13392 | | 2 | | 050-099, 155-156, 163-199, 275-299 | |
| 207B | 20 | VG | F | 20-0 | 32-45-13 | D05028P | | 25 | | | D13392 | CAP | Y | | 157-162 | |
| 207R | 20 | VG | F | 0-0 | 32-45-13 | D05028P | | 26 | | | D13392 | | 1 | | 050-099, 155-156, 163-199, 275-299 | |
| 207R | 20 | VG | F | 0-0 | 32-45-13 | D05028P | | 26 | | | D13392 | CAP | Y | | 157-162 | |
| 207Z | | | F | 0-0 | 32-45-13 | D05028P | | 27 | | | D13392 | | 3 | | 050-099, 155-156, 163-199, 275-299 | |
| 207Z | | | F | 0-0 | 32-45-13 | D05028P | | 27 | | | D13392 | DED | | | 157-162 | |
| 208B | 20 | VG | G | 20-0 | 32-45-13 | D05028P | | 28 | | | D13390 | | 2 | | 050-099, 155-156, 163-199, 275-299 | |
| 208B | 20 | VG | G | 20-0 | 32-45-13 | D05028P | | 28 | | | D13390 | CAP | Y | | 157-162 | |
| 208R | 20 | VG | G | 0-0 | 32-45-13 | D05028P | | 29 | | | D13390 | | 1 | | 050-099, 155-156, 163-199, 275-299 | |
| 208R | 20 | VG | G | 0-0 | 32-45-13 | D05028P | | 29 | | | D13390 | CAP | Y | | 157-162 | |
| 208Z | | | G | 0-0 | 32-45-13 | D05028P | | 30 | | | D13390 | | 3 | | 050-099, 155-156, 163-199, 275-299 | |
| 208Z | | | G | 0-0 | 32-45-13 | D05028P | | 30 | | | D13390 | DED | | | 157-162 | |
| 451G | 18 | UY | C | 14-0 | 32-46-11 | D05028P | | 8 | 4G | | D01706 | | 3 | 4H | ALL | |
| 451W | 18 | UY | C | 0-0 | 32-46-11 | D05028P | | 7 | 4K | | D01706 | | 1 | 4L | ALL | |
| 452G | 18 | UY | D | 14-0 | 32-46-11 | D05028P | | 10 | 4G | | D01710 | | 3 | 4H | ALL | |
| 452W | 18 | UY | D | 0-0 | 32-46-11 | D05028P | | 9 | 4K | | D01710 | | 1 | 4L | ALL | |
| A-A | | | E | 0-0 | 32-09-11 | D05028P | | 5 | | | S00245 | RED | | | ALL | |
| A-B | | | E | 0-0 | 32-09-11 | D05028P | | 6 | | | S00245 | BLU | | | ALL | |
| W0678 | 286T0678 | | | NOSE LANDING GEAR - (APU,LDNG LTS,PROX SNSR),P23/T-LINK/TPIS/TAXI LT | | | | | | | | | | | | |
| 001R | 18 | 8S | | 14-0 | 26-22-21 | D04950P | | 11 | | | D05936J | | 11 | | 050-099, 155-199, 275-299 | |
| 001R | 18 | 8S | | 14-0 | 26-22-21 | D04950P | | 11 | | | D05936P | | 11 | | 150-154 | |
| 002R | 18 | 8S | | 14-0 | 26-22-21 | D04950P | | 2 | | | D05936J | | 2 | | 050-099, 155-199, 275-299 | |
| 002R | 18 | 8S | | 14-0 | 26-22-21 | D04950P | | 2 | | | D05936P | | 2 | | 150-154 | |

WIRE LIST

D280T132

91-21-11

Section W0670

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0678 | 286T0678 | | | NOSE LANDING GEAR - (APU,LDNG LTS,PROX SNSR),P23/T-LINK/TPIS/TAXI LT (continued) | | | | | | | | | | | | | | |
| 003R | 18 | | 8S | 14-0 | 26-15-12 | D04950P | | 13 | | | | | D05936J | | 13 | | | 050-099, 155-199, 275-299 |
| 003R | 18 | | 8S | 14-0 | 26-15-12 | D04950P | | 13 | | | | | D05936P | | 13 | | | 150-154 |
| 004R | 18 | | 8S | 14-0 | 26-22-21 | D04950P | | 4 | | | | | D05936J | | 4 | | | 050-099, 155-199, 275-299 |
| 004R | 18 | | 8S | 14-0 | 26-22-21 | D04950P | | 4 | | | | | D05936P | | 4 | | | 150-154 |
| 005R | 18 | | 8S | 14-0 | 26-15-12 | D04950P | | 12 | | | | | D05936J | | 12 | | | 050-099, 155-199, 275-299 |
| 005R | 18 | | 8S | 14-0 | 26-15-12 | D04950P | | 12 | | | | | D05936P | | 12 | | | 150-154 |
| 006R | 18 | | 8S | 14-0 | 26-22-21 | D04950P | | 7 | | | | | D05936J | | 7 | | | 050-099, 155-199, 275-299 |
| 006R | 18 | | 8S | 14-0 | 26-22-21 | D04950P | | 7 | | | | | D05936P | | 7 | | | 150-154 |
| 007R | 18 | | 8S | 14-0 | 26-15-12 | D04950P | | 8 | | | | | D05936J | | 8 | | | 050-099, 155-199, 275-299 |
| 007R | 18 | | 8S | 14-0 | 26-15-12 | D04950P | | 8 | | | | | D05936P | | 8 | | | 150-154 |
| 008 | 18 | | 8R | 16-0 | 33-42-11 | D05040P | | 8 | | | | | TB5124 | | 1 | N | | 050-099, 155-199, 275-299 |
| 008 | 18 | | 8R | 11-0 | 33-42-11 | D05040P | | 8 | | | | | TB5124 | | 1 | N | | 150-154 |
| 009 | 10 | | UA | 16-0 | 33-42-11 | D05040P | | 9 | EN | | | | TB5124 | | 2 | N | | 050-099, 155-199, 275-299 |
| 009 | 10 | | UA | 11-0 | 33-42-11 | D05040P | | 9 | EN | | | | TB5124 | | 2 | N | | 150-154 |
| 010 | 18 | | 8R | 16-0 | 33-42-11 | D05040P | | 10 | | | | | TB5120 | | 1 | N | | 050-099, 155-199, 275-299 |
| 010 | 18 | | 8R | 11-0 | 33-42-11 | D05040P | | 10 | | | | | TB5120 | | 1 | N | | 150-154 |
| 011 | 10 | | UA | 16-0 | 33-42-11 | D05040P | | 11 | EN | | | | TB5120 | | 2 | N | | 050-099, 155-199, 275-299 |
| 011 | 10 | | UA | 11-0 | 33-42-11 | D05040P | | 11 | EN | | | | TB5120 | | 2 | N | | 150-154 |
| 012 | 18 | | 8R | 14-0 | 23-43-11 | D05850P | | 1 | | | | | D05938J | | 1 | | | 050-099, 155-199, 275-299 |
| 012 | 18 | | 8R | 14-0 | 23-43-11 | D05850P | | 1 | | | | | D05938P | | 1 | | | 150-154 |
| 013 | 18 | | 8R | 14-0 | 23-43-11 | D05850P | | 2 | | | | | D05938J | | 2 | | | 050-099, 155-199, 275-299 |
| 013 | 18 | | 8R | 14-0 | 23-43-11 | D05850P | | 2 | | | | | D05938P | | 2 | | | 150-154 |
| 014R | 18 | | 8S | 14-0 | 26-15-12 | D04950P | | 14 | | | | | D05936J | | 14 | | | 050-099, 155-199, 275-299 |
| 014R | 18 | | 8S | 14-0 | 26-15-12 | D04950P | | 14 | | | | | D05936P | | 14 | | | 150-154 |
| 015 | 18 | | 8R | 14-0 | 33-51-21 | D05850P | | 9 | | | | | D05938J | | 9 | | | 050-099, 155-199, 275-299 |
| 015 | 18 | | 8R | 14-0 | 33-51-21 | D05850P | | 9 | | | | | D05938P | | 9 | | | 150-154 |

WIRE LIST
D280T132

91-21-11
Section W0670
Page 5
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|-------|------|---------|--------|----|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W0678 | 286T0678 | | | | NOSE LANDING GEAR - (APU,LDNG LTS,PROX SNSR),P23/T-LINK/TPIS/TAXI LT (continued) | | | | | | | | | | | | | |
| 016 | 18 | | 8R | | 14-0 | 33-51-21 | D05850P | | 10 | | | | D05938J | | 10 | | | 050-099, 155-199, 275-299 |
| 016 | 18 | | 8R | | 14-0 | 33-51-21 | D05850P | | 10 | | | | D05938P | | 10 | | | 150-154 |
| 017 | 18 | | 8R | | 14-0 | 33-51-21 | D05850P | | 11 | | | | D05938J | | 11 | | | 050-099, 155-199, 275-299 |
| 017 | 18 | | 8R | | 14-0 | 33-51-21 | D05850P | | 11 | | | | D05938P | | 11 | | | 150-154 |
| 018 | 18 | | 8R | | 14-0 | 33-31-11 | D05850P | | 12 | | | | D05938J | | 12 | | | 050-099, 155-199, 275-299 |
| 018 | 18 | | 8R | | 14-0 | 33-31-11 | D05850P | | 12 | | | | D05938P | | 12 | | | 150-154 |
| 019 | 18 | | 8R | | 14-0 | 33-31-11 | D05850P | | 13 | | | | D05938J | | 13 | | | 050-099, 155-199, 275-299 |
| 019 | 18 | | 8R | | 14-0 | 33-31-11 | D05850P | | 13 | | | | D05938P | | 13 | | | 150-154 |
| 021R | 18 | | 8S | | 14-0 | 49-61-11 | D04950P | | 6 | | | | D05936J | | 6 | | | 050-099, 155-199, 275-299 |
| 021R | 18 | | 8S | | 14-0 | 49-61-11 | D04950P | | 6 | | | | D05936P | | 6 | | | 150-154 |
| 022R | 18 | | 8S | | 15-0 | 26-22-21 | D04950P | | 9 | | | | D05936J | | 9 | | | 275-276 |
| 022R | 18 | | 8S | | 14-0 | 26-22-21 | D04950P | | 9 | | | | D05936J | | 9 | | | 277-299 |
| 023R | 18 | | 8S | | 15-0 | 26-22-21 | D04950P | | 10 | | | | D05936J | | 10 | | | 275-276 |
| 023R | 18 | | 8S | | 14-0 | 26-22-21 | D04950P | | 10 | | | | D05936J | | 10 | | | 277-299 |
| 024 | 10 | | UA | | 16-0 | 33-42-11 | D05040P | | 12 | EN | | | TB5124 | | 6 | N | | 050-099, 155-199, 275-299 |
| 024 | 10 | | UA | | 11-0 | 33-42-11 | D05040P | | 12 | EN | | | TB5124 | | 6 | N | | 150-154 |
| 025 | 14 | | 5A | | 16-0 | 33-42-21 | D05040P | | 1 | | | | TB5124 | | 5 | N | | 050-099, 155-199, 275-299 |
| 025 | 14 | | 5A | | 11-0 | 33-42-21 | D05040P | | 1 | | | | TB5124 | | 5 | N | | 150-154 |
| 026 | 18 | | 8R | | 16-0 | 33-42-21 | D05040P | | 2 | | | | TB5124 | | 4 | N | | 050-099, 155-199, 275-299 |
| 026 | 18 | | 8R | | 11-0 | 33-42-21 | D05040P | | 2 | | | | TB5124 | | 4 | N | | 150-154 |
| 027 | 18 | | 8R | | 16-0 | 33-42-21 | D05040P | | 5 | | | | TB5120 | | 4 | N | | 050-099, 155-199, 275-299 |
| 027 | 18 | | 8R | | 11-0 | 33-42-21 | D05040P | | 5 | | | | TB5120 | | 4 | N | | 150-154 |
| 028 | 14 | | 5A | | 16-0 | 33-42-21 | D05040P | | 6 | | | | TB5120 | | 5 | N | | 050-099, 155-199, 275-299 |
| 028 | 14 | | 5A | | 11-0 | 33-42-21 | D05040P | | 6 | | | | TB5120 | | 5 | N | | 150-154 |
| 029 | 12 | | 5A | | 16-0 | 33-42-21 | D05040P | | 7 | | | | TB5120 | | 6 | N | | 050-099, 155-199, 275-299 |
| 029 | 12 | | 5A | | 11-0 | 33-42-21 | D05040P | | 7 | | | | TB5120 | | 6 | N | | 150-154 |
| 201B | 18 | | 8J | A | 13-0 | 32-09-12 | D05850P | | 16 | | | | D01756J | | 2 | | | 050-099, 155-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0670

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0678 | 286T0678 | | | NOSE LANDING GEAR - (APU,LDNG LTS,PROX SNSR),P23/T-LINK/TPIS/TAXI LT (continued) | | | | | | | | | | | |
| 201B | 18 | | 8J | A | 10-8 | 32-09-12 | D05850P | | | | D01756J | | 2 | | 150-154 |
| 201R | 18 | | 8J | A | 0-0 | 32-09-12 | D05850P | | | | D01756J | | 1 | | ALL |
| 202B | 18 | | 8J | B | 13-0 | 32-09-11 | D05040P | | | | D01754J | | 2 | | 050-099, 155-199, 275-299 |
| 202B | 18 | | 8J | B | 10-8 | 32-09-11 | D05040P | | | | D01754J | | 2 | | 150-154 |
| 202R | 18 | | 8J | B | 0-0 | 32-09-11 | D05040P | | | | D01754J | | 1 | | ALL |
| 204B | 20 | | 8K | D | 14-0 | 23-41-11 | D05850P | | | | D05938J | | 3 | | 050-099, 155-199, 275-299 |
| 204B | 20 | | 8K | D | 14-0 | 23-41-11 | D05850P | | | | D05938P | | 3 | | 150-154 |
| 204R | 20 | | 8K | D | 0-0 | 23-41-11 | D05850P | | | | D05938J | | 4 | | 050-099, 155-199, 275-299 |
| 204R | 20 | | 8K | D | 0-0 | 23-41-11 | D05850P | | | | D05938P | | 4 | | 150-154 |
| 204Z | | | | D | 0-0 | 23-41-11 | D05850P | | | | D05938J | | 5 | | 050-099, 155-199, 275-299 |
| 204Z | | | | D | 0-0 | 23-41-11 | D05850P | | | | D05938P | | 5 | | 150-154 |
| 205B | 20 | | 8K | E | 14-0 | 23-51-11 | D05850P | | | | D05938J | | 6 | | 050-099, 155-199, 275-299 |
| 205B | 20 | | 8K | E | 14-0 | 23-51-11 | D05850P | | | | D05938P | | 6 | | 150-154 |
| 205R | 20 | | 8K | E | 0-0 | 23-51-11 | D05850P | | | | D05938J | | 7 | | 050-099, 155-199, 275-299 |
| 205R | 20 | | 8K | E | 0-0 | 23-51-11 | D05850P | | | | D05938P | | 7 | | 150-154 |
| 205Z | | | | E | 0-0 | 23-51-11 | D05850P | | | | D05938J | | 8 | | 050-099, 155-199, 275-299 |
| 205Z | | | | E | 0-0 | 23-51-11 | D05850P | | | | D05938P | | 8 | | 150-154 |
| 207B | 20 | | VG | F | 16-0 | 32-45-12 | D06106P | | | | D04950P | | 15 | | 050-099, 155-199, 275-299 |
| 207R | 20 | | VG | F | 0-0 | 32-45-12 | D06106P | | | | D04950P | | 16 | | 050-099, 155-199, 275-299 |
| 207Z | | | | F | 0-0 | 32-45-12 | D06106P | | | | D04950P | | 1 | | 050-099, 155-199, 275-299 |
| 208B | 20 | | VG | G | 16-0 | 32-45-12 | D06106P | | | | D05850P | | 17 | | 050-099, 155-199, 275-299 |
| 208R | 20 | | VG | G | 0-0 | 32-45-12 | D06106P | | | | D05850P | | 18 | | 050-099, 155-199, 275-299 |
| 208Z | | | | G | 0-0 | 32-45-12 | D06106P | | | | D05850P | | 14 | | 050-099, 155-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0670
Page 7 End
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0680 | 286T0680 | | | R WW ADP HYD PRESS. & CONT PRESS. SW,RAT. PRESS. SW & TACH | | | | | | | | | | | | | |
| 002 | 18 | | UA | 9-8 | 29-21-31 | D04316P | | 2 | | | | | S00366 | 1 | C | | ALL |
| 005 | 18 | | UA | 9-8 | 29-21-31 | D04316P | | 5 | | | | | S00366 | 2 | C | | ALL |
| 006 | 18 | | UA | 10-5 | 29-21-31 | D04316P | | 6 | | | | | D02358 | 1 | | | ALL |
| 007 | 18 | | UA | 10-5 | 29-21-31 | D04316P | | 7 | | | | | D02358 | 2 | | | ALL |
| 008 | 18 | | UA | 13-2 | 29-11-32 | D04316P | | 8 | | | | | D00478 | 2 | | | ALL |
| 009 | 18 | | UA | 13-2 | 29-11-32 | D04316P | | 9 | | | | | D00478 | 3 | | | ALL |
| 010 | 18 | | 5A | 10-8 | 29-21-31 | D02356 | | 3 | | | | | D04316P | 11 | | | ALL |
| 012 | 18 | | 5A | 1-6 | 29-21-31 | D04316P | | | | | FA | | GD04302 | S.. | N | | ALL |
| 013 | 18 | | 5A | 1-6 | 29-21-31 | D04316P | | 1 | | | | | GD04302 | S.. | N | | ALL |
| 201B | 18 | | VG | A | 10-8 | 29-21-31 | D02356 | | 2 | | | | D04316P | 4 | | | ALL |
| 201R | 18 | | VG | A | 0-0 | 29-21-31 | D02356 | | 1 | | | | D04316P | 3 | | | ALL |
| 201Z | | | | A | 0-0 | 29-21-31 | D02356 | | DED | | | | D04316P | | | FA | ALL |
| W0682 | 286T0682 | | | MAIN LANDING GEAR (UPPER) RIGHT - BRAKE TEMP,TPIS | | | | | | | | | | | | | |
| 201B | 18 | | 8J | A | 9-0 | 32-61-12 | D05030J | | 2 | | | | D02208J | 2 | | | ALL |
| 201R | 18 | | 8J | A | 0-0 | 32-61-12 | D05030J | | 1 | | | | D02208J | 1 | | | ALL |
| 202B | 18 | | 8J | B | 9-0 | 32-61-12 | D05030J | | 4 | | | | D02210J | 2 | | | ALL |
| 202R | 18 | | 8J | B | 0-0 | 32-61-12 | D05030J | | 3 | | | | D02210J | 1 | | | ALL |
| 203B | 18 | | 8J | C | 9-0 | 32-09-12 | D05030J | | 6 | | | | D05032J | 6 | | | ALL |
| 203R | 18 | | 8J | C | 0-0 | 32-09-12 | D05030J | | 5 | | | | D05032J | 5 | | | ALL |
| 204B | 20 | | 8K | D | 9-0 | 32-42-11 | D05030J | | 8 | | | | D05032J | 8 | | | ALL |
| 204R | 20 | | 8K | D | 0-0 | 32-42-11 | D05030J | | 7 | | | | D05032J | 7 | | | ALL |
| 204Z | | | | D | 0-0 | 32-42-11 | D05030J | | 17 | | | | D05032J | 9 | | | ALL |
| 205B | 20 | | 8K | E | 9-0 | 32-42-11 | D05030J | | 10 | | | | D05032J | 2 | | | ALL |
| 205R | 20 | | 8K | E | 0-0 | 32-42-11 | D05030J | | 9 | | | | D05032J | 1 | | | ALL |
| 205Z | | | | E | 0-0 | 32-42-11 | D05030J | | 18 | | | | D05032J | 3 | | | ALL |
| 207B | 20 | | VG | H | 9-0 | 32-45-14 | D05030J | | 15 | | | | D05032J | 25 | | | 050-099, 155-199, 275-299 |
| 207R | 20 | | VG | H | 0-0 | 32-45-14 | D05030J | | 16 | | | | D05032J | 26 | | | 050-099, 155-199, 275-299 |
| 207Z | | | | H | 0-0 | 32-45-14 | D05030J | | 19 | | | | D05032J | 27 | | | 050-099, 155-199, 275-299 |
| 208B | 20 | | VG | J | 9-0 | 32-45-14 | D05030J | | 28 | | | | D05032J | 28 | | | 050-099, 155-199, 275-299 |
| 208R | 20 | | VG | J | 0-0 | 32-45-14 | D05030J | | 29 | | | | D05032J | 29 | | | 050-099, 155-199, 275-299 |
| 208Z | | | | J | 0-0 | 32-45-14 | D05030J | | 30 | | | | D05032J | 30 | | | 050-099, 155-199, 275-299 |
| 301B | 20 | | UC | CO | 9-0 | 27-62-11 | D05032J | | 15 | | | | D05030J | 20 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0680

Page 1

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0682 | 286T0682 | | | MAIN LANDING GEAR (UPPER) RIGHT - BRAKE TEMP, TPIS (continued) | | | | | | | | | | | |
| 301R | 20 | UC | CO | | 0-0 | 27-62-11 | D05032J | 16 | | | D05030J | 21 | | | ALL |
| 301Y | 20 | UC | CO | | 0-0 | 27-62-11 | D05032J | 17 | | | D05030J | 22 | | | ALL |
| 451G | 18 | UY | F | | 9-0 | 32-46-11 | D05030J | 12 | 4G | | D05032J | 12 | 4H | | ALL |
| 451W | 18 | UY | F | | 0-0 | 32-46-11 | D05030J | 11 | 4K | | D05032J | 11 | 4L | | ALL |
| 452G | 18 | UY | G | | 9-0 | 32-46-11 | D05030J | 14 | 4G | | D05032J | 14 | 4H | | ALL |
| 452W | 18 | UY | G | | 0-0 | 32-46-11 | D05030J | 13 | 4K | | D05032J | 13 | 4L | | ALL |
| W0683 | 286T0683 | | | HF L,SHELF TO CONTROL PANEL | | | | | | | | | | | |
| 001 | 18 | PA | | | 7-0 | 33-13-16 | D00733 | 1 | DK | | TB0068G | 5 | 2 | | ALL |
| 002 | 18 | PA | | | 6-0 | 33-13-16 | D00733 | 2 | DK | | GD00263 | A.. | 2 | | ALL |
| 003 | 22 | PA | | | 47-0 | 23-11-11 | D00733 | 3 | | | D04653J | 3 | | | ALL |
| 004 | 20 | PA | | | 6-0 | 23-11-11 | D00733 | 4 | | | GD00263 | A.. | 2 | | ALL |
| 005 | 24 | PK | | | 47-0 | 23-11-11 | D00733 | 5 | | | D04653J | 5 | | | ALL |
| 013 | 24 | PK | | | 47-0 | 23-11-11 | D00733 | 13 | | | D04653J | 4 | | | ALL |
| 014 | 24 | PK | | | 47-0 | 23-11-11 | D00733 | 14 | | | D04653J | 6 | | | ALL |
| 017 | 24 | PK | | | 45-0 | 23-25-14 | D04653J | 1 | | | TB0064F | A011 | 2 | | 156-157, 166-199, 277-299 |
| 018 | 24 | PK | | | 45-0 | 23-25-14 | D04653J | 2 | | | TB0064F | C011 | 2 | | 156-157, 166-199, 277-299 |
| 019 | 24 | PK | | | 45-0 | 23-25-14 | D04653J | 12 | | | TB0064F | A016 | 2 | | 156-157, 166-199, 277-299 |
| 201 | 20 | UA | | | 1-6 | 23-11-11 | D00733 | | | FA | GD00631 | S.. | E | | ALL |
| 201B | 24 | PW | IA | | 47-0 | 23-11-11 | D00733 | 10 | | | D04653J | 10 | | | ALL |
| 201R | 24 | PW | IA | | 0-0 | 23-11-11 | D00733 | 9 | | | D04653J | 9 | | | ALL |
| 201Z | | | IA | | 0-0 | 23-11-11 | D00733 | | | FA | D04653J | 11 | | | ALL |
| FRA | | | | | 0-0 | 23-11-11 | D00733 | 11 | | | D00733 | | | FA | ALL |
| FRB | | | | | 0-0 | 23-11-11 | D00733 | 15 | | | D00733 | | | FA | ALL |
| W0684 | 286T0684 | | | MAIN LANDING GEAR (UPPER) RIGHT - BRAKE TEMP, TPIS | | | | | | | | | | | |
| 201B | 18 | 8J | A | | 9-0 | 32-61-12 | D05034J | 2 | | | D02204J | 2 | | | ALL |
| 201R | 18 | 8J | A | | 0-0 | 32-61-12 | D05034J | 1 | | | D02204J | 1 | | | ALL |
| 202B | 18 | 8J | B | | 9-0 | 32-61-12 | D05034J | 4 | | | D02206J | 2 | | | ALL |
| 202R | 18 | 8J | B | | 0-0 | 32-61-12 | D05034J | 3 | | | D02206J | 1 | | | ALL |
| 203B | 18 | 8J | C | | 9-0 | 32-09-11 | D05034J | 6 | | | D05036J | 6 | | | ALL |
| 203R | 18 | 8J | C | | 0-0 | 32-09-11 | D05034J | 5 | | | D05036J | 5 | | | ALL |
| 204B | 20 | 8K | D | | 9-0 | 32-42-11 | D05034J | 8 | | | D05036J | 8 | | | ALL |
| 204R | 20 | 8K | D | | 0-0 | 32-42-11 | D05034J | 7 | | | D05036J | 7 | | | ALL |
| 204Z | | | D | | 0-0 | 32-42-11 | D05034J | 15 | | | D05036J | 9 | | | ALL |
| 205B | 20 | 8K | E | | 9-0 | 32-42-11 | D05034J | 10 | | | D05036J | 2 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0680
Page 2
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|----|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0684 | 286T0684 | | | MAIN LANDING GEAR (UPPER) RIGHT - BRAKE TEMP, TPIS (continued) | | | | | | | | | | | | | |
| 205R | 20 | 8K | E | 0-0 | 32-42-11 | D05034J | | 9 | | | | | D05036J | 1 | | | ALL |
| 205Z | | | E | 0-0 | 32-42-11 | D05034J | | 16 | | | | | D05036J | 3 | | | ALL |
| 207B | 20 | VG | H | 9-0 | 32-45-14 | D05034J | | 25 | | | | | D05036J | 25 | | | 050-099, 155-199, 275-299 |
| 207R | 20 | VG | H | 0-0 | 32-45-14 | D05034J | | 26 | | | | | D05036J | 26 | | | 050-099, 155-199, 275-299 |
| 207Z | | | H | 0-0 | 32-45-14 | D05034J | | 27 | | | | | D05036J | 27 | | | 050-099, 155-199, 275-299 |
| 208B | 20 | VG | J | 9-0 | 32-45-14 | D05034J | | 28 | | | | | D05036J | 28 | | | 050-099, 155-199, 275-299 |
| 208R | 20 | VG | J | 0-0 | 32-45-14 | D05034J | | 29 | | | | | D05036J | 29 | | | 050-099, 155-199, 275-299 |
| 208Z | | | J | 0-0 | 32-45-14 | D05034J | | 30 | | | | | D05036J | 30 | | | 050-099, 155-199, 275-299 |
| 451G | 18 | UY | F | 9-0 | 32-46-11 | D05034J | | 12 | 4G | | | | D05036J | 12 | 4H | | ALL |
| 451W | 18 | UY | F | 0-0 | 32-46-11 | D05034J | | 11 | 4K | | | | D05036J | 11 | 4L | | ALL |
| 452G | 18 | UY | G | 9-0 | 32-46-11 | D05034J | | 14 | 4G | | | | D05036J | 14 | 4H | | ALL |
| 452W | 18 | UY | G | 0-0 | 32-46-11 | D05034J | | 13 | 4K | | | | D05036J | 13 | 4L | | ALL |
| W0685 | 286T0685 | | | ATC-L TRANSPONDER,SHELF TO CONT PNL | | | | | | | | | | | | | |
| 001 | 20 | PA | | 2-0 | 33-13-18 | SP02272 | | 9 | | | | | D00303 | 1 | | | 050-099, 150-155, 162-165, 275-276 |
| 002 | 20 | PA | | 1-6 | 33-13-18 | GD04472 | | A.. | 2 | | | | D00303 | 2 | | | 050-099, 150-155, 162-165 |
| 002 | 20 | PA | | 1-6 | 33-13-18 | GD04454 | | A.. | 2 | | | | D00303 | 2 | | | 275-276 |
| 003 | 22 | PA | | 32-0 | 34-53-11 | D04695J | | 3 | | | | | D00303 | 3 | | | ALL |
| 004 | 20 | PA | | 9-0 | 34-53-11 | GD02464 | | A.. | 2 | | | | D00303 | 4 | | | 050-099, 150-199 |
| 004 | 20 | PA | | 3-3 | 34-53-11 | GD04454 | | A.. | 2 | | | | D00303 | 4 | | | 275-299 |
| 007 | 24 | PK | | 32-0 | 34-53-11 | D04695J | | 7 | | | | | D00303 | 20 | | | ALL |
| 008 | 20 | PA | | 3-3 | 34-53-11 | GD04454 | | D.. | 2 | | | | D00303 | 8 | | | 050-099, 155-199, 275-299 |
| 008 | 20 | PA | | 3-3 | 34-53-11 | GD04472 | | D.. | 2 | | | | D00303 | 8 | | | 150-154 |
| 009 | 24 | PK | | 32-0 | 34-53-11 | D04695J | | 9 | | | | | D00303 | 9 | | | 050-099, 150-156, 162-166, 275-276 |
| 010 | 24 | PK | | 32-0 | 34-53-11 | D04695J | | 1 | | | | | D00303 | 10 | | | 050-099 |
| 010 | 24 | PK | | 32-0 | 34-53-11 | D00303 | | 10 | | | | | D04695J | 1 | | | 150-199, 275-299 |
| 012 | 24 | PK | | 32-0 | 34-53-11 | D00303 | | 7 | | | | | D04695J | 6 | | | 050-099, 150-154 |
| 012 | 24 | PK | | 32-0 | 34-53-11 | D04695J | | 6 | | | | | D00303 | 7 | | | 155-199, 275-299 |
| 015 | 24 | PK | | 25-0 | 31-51-33 | D04695J | | 15 | | | | | TB0031F | C024 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0680

Page 3

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0685 | 286T0685 | | | ATC-L TRANSPONDER,SHELF TO CONT PNL (continued) | | | | | | | | | | | |
| 016 | 24 | | PK | 32-0 | 34-53-11 | D00303 | | 15 | | | D04695J | | 8 | | 050-099 |
| 016 | 24 | | PK | 32-0 | 34-53-11 | D04695J | | 8 | | | D00303 | | 15 | | 150-199, 275-299 |
| 017 | 20 | | PA | 3-3 | 34-53-11 | D00303 | | 6 | | | GD04454 | D.. | 2 | | 050-099, 155-199, 275-299 |
| 017 | 20 | | PA | 3-3 | 34-53-11 | D00303 | | 6 | | | GD04472 | D.. | 2 | | 150-154 |
| 018 | 22 | | PA | 11-0 | 33-16-18 | TB0031H | | 8 | 2 | | D00303 | | 18 | | ALL |
| 021 | 22 | | PA | 11-0 | 33-16-18 | TB0031H | | 6 | 2 | | D00303 | | 21 | | ALL |
| 022 | 24 | | PK | 32-0 | 34-53-11 | D00303 | | 12 | | | D04695J | | 2 | | 050-099, 150-152, 155-199, 275-299 |
| 024 | 24 | | PK | 32-0 | 34-53-11 | D00303 | | 24 | | | D04695J | | 5 | | 050-099 |
| 024 | 24 | | PK | 32-0 | 34-53-11 | D04695J | | 5 | | | D00303 | | 24 | | 150-199, 275-299 |
| 025 | 24 | | PK | 32-0 | 34-53-11 | D00303 | | 11 | | | D04695J | | 16 | | 157, 167-199, 277-299 |
| 026 | 24 | | PK | 32-0 | SPARE | D04695J | | 17 | | | D00303 | REF | JW | | 157, 167-199, 277-299 |
| 027 | 24 | | PK | 32-0 | SPARE | D04695J | | 18 | | | D00303 | REF | JW | | 157, 167-199, 277-299 |
| 201 | 20 | | UA | 1-6 | 34-53-11 | D00303 | | | | IA | GD04454 | S.. | 2 | | 050-099 |
| 201 | 20 | | UA | 1-6 | 34-53-11 | D00303 | | | | IA | GD04472 | S.. | 2 | | 150-154 |
| 201 | 20 | | UA | 3-3 | 34-53-11 | D00303 | | | | IA | GD04454 | S.. | 2 | | 155-199 |
| 201 | 20 | | UA | 3-3 | 34-53-11 | D00303 | REF | | | IA | GD04454 | S.. | 2 | | 275-299 |
| 201B | 24 | | PW | IA | 31-7 | 34-53-11 | D04695J | | 11 | | D00303 | | 23 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-53-11 | D04695J | | 10 | | D00303 | | 22 | | ALL |
| 201Z | | | | IA | 0-0 | 34-53-11 | D04695J | | 12 | | D00303 | | | IA | 050-099, 150-199 |
| 201Z | | | | IA | 0-0 | 34-53-11 | D04695J | | 12 | | D00303 | REF | | IA | 275-299 |
| 203B | 20 | | PB | IC | 3-0 | 33-13-18 | SP04098 | | 9 | | D00303 | | 2 | | 156-157, 166-199, 277-299 |
| 203R | 20 | | PB | IC | 0-0 | 33-13-18 | SP02272 | | 9 | | D00303 | | 1 | | 156-157, 166-199, 277-299 |
| W0686 | 286T0686 | | | MAIN LANDING GEAR (LOWER) RIGHT - BRAKE TEMP, TPIS | | | | | | | | | | | |
| 201B | 20 | | 8K | B | 20-0 | 32-42-11 | D05036P | | 8 | | D02020 | | 3 | | 050-099, 155-199, 275-299 |
| 201B | 20 | | 8K | B | 18-0 | 32-42-11 | D05036P | | 8 | | D02020 | | 3 | | 150-154 |
| 201R | 20 | | 8K | B | 0-0 | 32-42-11 | D05036P | | 7 | | D02020 | | 1 | | ALL |
| 201Z | | | | B | 0-0 | 32-42-11 | D05036P | | 9 | | D02020 | DED | | | ALL |
| 202B | 20 | | 8K | C | 20-0 | 32-42-11 | D05036P | | 2 | | D02022 | | 3 | | 050-099, 155-199, 275-299 |
| 202B | 20 | | 8K | C | 18-0 | 32-42-11 | D05036P | | 2 | | D02022 | | 3 | | 150-154 |
| 202R | 20 | | 8K | C | 0-0 | 32-42-11 | D05036P | | 1 | | D02022 | | 1 | | ALL |
| 202Z | | | | C | 0-0 | 32-42-11 | D05036P | | 3 | | D02022 | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0680

Page 4

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|------|---|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0686 | 286T0686 | | | | MAIN LANDING GEAR (LOWER) RIGHT - BRAKE TEMP, TPIS (continued) | | | | | | | | | | |
| 207B | 20 | VG | F | 20-0 | 32-45-14 | D05036P | | 25 | | | D13388 | | 2 | | 050-099, 155-156, 163-199, 275-299 |
| 207B | 20 | VG | F | 20-0 | 32-45-14 | D05036P | | 25 | | | D13388 | CAP | Y | | 157-162 |
| 207R | 20 | VG | F | 0-0 | 32-45-14 | D05036P | | 26 | | | D13388 | | 1 | | 050-099, 155-156, 163-199, 275-299 |
| 207R | 20 | VG | F | 0-0 | 32-45-14 | D05036P | | 26 | | | D13388 | CAP | Y | | 157-162 |
| 207Z | | | F | 0-0 | 32-45-14 | D05036P | | 27 | | | D13388 | | 3 | | 050-099, 155-156, 163-199, 275-299 |
| 207Z | | | F | 0-0 | 32-45-14 | D05036P | | 27 | | | D13388 | DED | | | 157-162 |
| 208B | 20 | VG | G | 20-0 | 32-45-14 | D05036P | | 28 | | | D13386 | | 2 | | 050-099, 155-156, 163-199, 275-299 |
| 208B | 20 | VG | G | 20-0 | 32-45-14 | D05036P | | 28 | | | D13386 | CAP | Y | | 157-162 |
| 208R | 20 | VG | G | 0-0 | 32-45-14 | D05036P | | 29 | | | D13386 | | 1 | | 050-099, 155-156, 163-199, 275-299 |
| 208R | 20 | VG | G | 0-0 | 32-45-14 | D05036P | | 29 | | | D13386 | CAP | Y | | 157-162 |
| 208Z | | | G | 0-0 | 32-45-14 | D05036P | | 30 | | | D13386 | | 3 | | 050-099, 155-156, 163-199, 275-299 |
| 208Z | | | G | 0-0 | 32-45-14 | D05036P | | 30 | | | D13386 | DED | | | 157-162 |
| 451G | 18 | UY | D | 14-0 | 32-46-11 | D05036P | | 12 | 4G | | D01708 | | 3 | 4H | ALL |
| 451W | 18 | UY | D | 0-0 | 32-46-11 | D05036P | | 11 | 4K | | D01708 | | 1 | 4L | ALL |
| 452G | 18 | UY | E | 14-0 | 32-46-11 | D05036P | | 14 | 4G | | D01712 | | 3 | 4H | ALL |
| 452W | 18 | UY | E | 0-0 | 32-46-11 | D05036P | | 13 | 4K | | D01712 | | 1 | 4L | ALL |
| A-A | | | A | 0-0 | 32-09-11 | D05036P | | 5 | | | S00246 | RED | | | ALL |
| A-B | | | A | 0-0 | 32-09-11 | D05036P | | 6 | | | S00246 | BLU | | | ALL |
| W0687 | 286T0687 | | | | ATC-R TRANSPONDER,SHELF TO CONT PNL | | | | | | | | | | |
| 001 | 24 | PK | | 26-0 | 31-51-33 | D04697J | | 1 | | | TB0031F | C026 | 2 | | 050-099 |
| 001 | 24 | PK | | 27-0 | 31-51-33 | D04697J | | 1 | | | TB0031F | C026 | 2 | | 150-199, 275-299 |
| 002 | 22 | PA | | 26-0 | 31-31-26 | TB0255X | B001 | BJ | | | D04697J | | 4 | | 050-099 |
| 002 | 22 | PA | | 27-0 | 31-31-26 | TB0255X | B001 | BJ | | | D04697J | | 4 | | 150-199, 275-299 |
| 003 | 22 | PA | | 25-0 | 34-53-21 | D04697J | | 3 | | | D00305 | | 3 | | ALL |
| 004 | 20 | PA | | 3-3 | 34-53-21 | GD04454 | A.. | 2 | | | D00305 | | 4 | | 050-099, 155-199, 275-299 |
| 004 | 20 | PA | | 3-3 | 34-53-21 | GD04472 | A.. | 2 | | | D00305 | | 4 | | 150-154 |
| 005 | 22 | PA | | 25-0 | 34-53-13 | D04697J | | 5 | | | D00305 | | 5 | | ALL |
| 007 | 24 | PK | | 25-0 | 34-53-21 | D04697J | | 7 | | | D00305 | | 5 | | ALL |
| 008 | 20 | PA | | 3-3 | 34-53-21 | GD04454 | D.. | 2 | | | D00305 | | 8 | | 050-099, 155-199, 275-299 |
| 008 | 20 | PA | | 3-3 | 34-53-21 | GD04472 | D.. | 2 | | | D00305 | | 8 | | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0680

Page 5

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0687 | 286T0687 | | | ATC-R TRANSPONDER,SHELF TO CONT PNL (continued) | | | | | | | | | | | |
| 009 | 24 | | PK | | 25-0 | 34-53-21 | D04697J | | 9 | | D00305 | | 9 | | 050-099, 150-156, 162-166, 275-276 |
| 010 | 20 | | PA | | 3-3 | 34-53-21 | D00305 | | 6 | | GD04454 | | D.. | 2 | 050-099, 155-199, 275-299 |
| 010 | 20 | | PA | | 3-3 | 34-53-21 | GD04472 | | D.. | 2 | D00305 | | 6 | | 150-154 |
| 012 | 24 | | PK | | 25-0 | 34-53-21 | D00305 | | 7 | | D04697J | | 6 | | 050-099 |
| 012 | 24 | | PK | | 25-0 | 34-53-21 | D04697J | | 6 | | D00305 | | 7 | | 150-199, 275-299 |
| 013 | 24 | | PK | | 25-0 | 34-53-21 | D00305 | | 12 | | D04697J | | 13 | | 050-099, 150-152, 155-199, 275-299 |
| 015 | 24 | | PK | | 25-0 | 34-53-21 | D00305 | | 15 | | D04697J | | 8 | | 050-099 |
| 015 | 24 | | PK | | 25-0 | 34-53-21 | D04697J | | 8 | | D00305 | | 15 | | 150-199, 275-299 |
| 016 | 24 | | PK | | 25-0 | 34-53-21 | D04697J | | 16 | | D00305 | | 11 | | 157, 167-199, 277-299 |
| 017 | 24 | | PK | | 25-0 | SPARE | D04697J | | 17 | | D00305 | REF | JW | | 157, 167-199, 277-299 |
| 018 | 22 | | PA | | 11-0 | 33-16-18 | TB0031G | | 27 | 2 | D00305 | | 18 | | 150-154, 275 |
| 018 | 22 | | PA | | 11-0 | 33-16-18 | TB0031G | | 27 | 2 | D00305 | CAP | Y | | 276-278 |
| 019 | 24 | | PK | | 25-0 | SPARE | D04697J | | 18 | | D00305 | REF | JW | | 157, 167-199, 277-299 |
| 024 | 24 | | PK | | 25-0 | 34-53-21 | D00305 | | 24 | | D04697J | | 2 | | 050-099, 155-199 |
| 024 | 24 | | PK | | 25-0 | 34-53-21 | D04697J | | 2 | | D00305 | | 24 | | 150-154, 275-299 |
| 201 | 20 | | UA | | 1-6 | 34-53-21 | D00305 | REF | | IA | GD04454 | | S.. | 2 | 050-099, 155-199, 275-299 |
| 201 | 20 | | UA | | 1-6 | 34-53-21 | D00305 | REF | | IA | GD04472 | | S.. | 2 | 150-154 |
| 201B | 24 | | PW | IA | 25-0 | 34-53-21 | D04697J | | 11 | | D00305 | | 23 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-53-21 | D04697J | | 10 | | D00305 | | 22 | | ALL |
| 201Z | | | | IA | 0-0 | 34-53-21 | D04697J | | 12 | | D00305 | REF | | IA | ALL |
| W0688 | 286T0688 | | | MAIN LANDING GEAR (LOWER) RIGHT- BRAKE TEMP,TPIS | | | | | | | | | | | |
| 201B | 20 | | 8K | B | 20-0 | 32-42-11 | D05032P | | 8 | | D02024 | | 3 | | ALL |
| 201R | 20 | | 8K | B | 0-0 | 32-42-11 | D05032P | | 7 | | D02024 | | 1 | | ALL |
| 201Z | | | | B | 0-0 | 32-42-11 | D05032P | | 9 | | D02024 | DED | | | ALL |
| 202B | 20 | | 8K | C | 20-0 | 32-42-11 | D05032P | | 2 | | D02026 | | 3 | | ALL |
| 202R | 20 | | 8K | C | 0-0 | 32-42-11 | D05032P | | 1 | | D02026 | | 1 | | ALL |
| 202Z | | | | C | 0-0 | 32-42-11 | D05032P | | 3 | | D02026 | DED | | | ALL |
| 207B | 20 | | VG | F | 20-0 | 32-45-14 | D05032P | | 25 | | D13380 | | 2 | | 050-099, 155-156, 163-199, 275-299 |
| 207B | 20 | | VG | F | 20-0 | 32-45-14 | D05032P | | 25 | | D13380 | CAP | Y | | 157-162 |
| 207R | 20 | | VG | F | 0-0 | 32-45-14 | D05032P | | 26 | | D13380 | | 1 | | 050-099, 155-156, 163-199, 275-299 |
| 207R | 20 | | VG | F | 0-0 | 32-45-14 | D05032P | | 26 | | D13380 | CAP | Y | | 157-162 |

WIRE LIST

D280T132

91-21-11

Section W0680

Page 6

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|-------|------|---------|--------|-------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0688 | 286T0688 | | | | MAIN LANDING GEAR (LOWER) RIGHT- BRAKE TEMP,TPIS (continued) | | | | | | | | | | | |
| 207Z | | | | F | 0-0 | 32-45-14 | D05032P | 27 | | | | | D13380 | 3 | DK | 050-099, 155-156, 163-199, 275-299 |
| 207Z | | | | F | 0-0 | 32-45-14 | D05032P | 27 | | | | | D13380 | | DED | 157-162 |
| 208B | 20 | VG | | G | 20-0 | 32-45-14 | D05032P | 28 | | | | | D13378 | 2 | | 050-099, 155-156, 163-199, 275-299 |
| 208B | 20 | VG | | G | 20-0 | 32-45-14 | D05032P | 28 | | | | | D13378 | | CAP Y | 157-162 |
| 208R | 20 | VG | | G | 0-0 | 32-45-14 | D05032P | 29 | | | | | D13378 | 1 | | 050-099, 155-156, 163-199, 275-299 |
| 208R | 20 | VG | | G | 0-0 | 32-45-14 | D05032P | 29 | | | | | D13378 | | CAP Y | 157-162 |
| 208Z | | | | G | 0-0 | 32-45-14 | D05032P | 30 | | | | | D13378 | 3 | DK | 050-099, 155-156, 163-199, 275-299 |
| 208Z | | | | G | 0-0 | 32-45-14 | D05032P | 30 | | | | | D13378 | | DED | 157-162 |
| 301B | 20 | UC | | CO | 15-0 | 27-62-11 | D23140 | A | | | | | D05032P | 15 | | ALL |
| 301R | 20 | UC | | CO | 0-0 | 27-62-11 | D23140 | C | | | | | D05032P | 16 | | ALL |
| 301Y | 20 | UC | | CO | 0-0 | 27-62-11 | D23140 | B | | | | | D05032P | 17 | | ALL |
| 451G | 18 | UY | | D | 15-0 | 32-46-11 | D05032P | 12 | 4G | | | | D01716 | 3 | 4H | ALL |
| 451W | 18 | UY | | D | 0-0 | 32-46-11 | D05032P | 11 | 4K | | | | D01716 | 1 | 4L | ALL |
| 452G | 18 | UY | | E | 15-0 | 32-46-11 | D05032P | 14 | 4G | | | | D01720 | 3 | 4H | ALL |
| 452W | 18 | UY | | E | 0-0 | 32-46-11 | D05032P | 13 | 4K | | | | D01720 | 1 | 4L | ALL |
| A-A | | | | A | 0-0 | 32-09-12 | D05032P | 5 | | | | | S00268 | | RED | ALL |
| A-B | | | | A | 0-0 | 32-09-12 | D05032P | 6 | | | | | S00268 | | BLU | ALL |
| W0689 | 286T0689 | | | | E2-5 TO P36 & P33 | | | | | | | | | | | |
| 001 | 24 | PK | | | 24-0 | 23-31-13 | D04709P | 1 | | | | | D05029J | 1 | | 050-099 |
| 001 | 24 | PK | | | 23-0 | 23-31-13 | D04709P | 1 | | | | | D05029J | 1 | | 150-199, 275-299 |
| 002 | 24 | PK | | | 24-0 | 23-31-13 | D04709P | 2 | | | | | D05029J | 2 | | 050-099 |
| 002 | 24 | PK | | | 23-0 | 23-31-13 | D04709P | 2 | | | | | D05029J | 2 | | 150-199, 275-299 |
| 003 | 24 | PK | | | 24-0 | 23-31-13 | D04709P | 3 | | | | | D05029J | 3 | | 050-099 |
| 003 | 24 | PK | | | 23-0 | 23-31-13 | D04709P | 3 | | | | | D05029J | 3 | | 150-199, 275-299 |
| 004 | 24 | PK | | | 23-0 | SPARE | D04709P | 4 | | | | | D05029J | 4 | | 150-199, 275-299 |
| 005 | 24 | PK | | | 23-0 | SPARE | D04709P | 5 | | | | | D05029J | 5 | | 150-199, 275-299 |
| 006 | 22 | PA | | | 11-0 | 23-34-11 | D04709P | 6 | | | | | D05193P | 1 | | ALL |
| 007 | 22 | PA | | | 24-0 | 23-34-11 | D05193P | 2 | | | | | SP00261 | | S | 050-099 |
| 007 | 22 | PA | | | 24-0 | 23-34-11 | D05193P | 2 | | | | | SP00261 | | 9 | 150-199, 275-299 |
| 008 | 22 | PA | | | 30-0 | 23-34-11 | D05193P | 3 | | | | | D05029J | 7 | | ALL |
| 009 | 22 | PA | | | 30-0 | 23-34-11 | D05193P | 4 | | | | | D05029J | 8 | | ALL |
| 010 | 16 | PA | | | 11-0 | 23-34-15 | D04709P | 15 | | | | | D05191P | 1 | | ALL |
| 011 | 16 | PA | | | 11-0 | 23-34-16 | D04709P | 19 | | | | | D05191P | 2 | | ALL |
| 012 | 12 | PA | | | 11-0 | 23-34-18 | D04709P | 23 | | | | | D05191P | 3 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0680

Page 7

Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0689 | 286T0689 | | | E2-5 TO P36 & P33 (continued) | | | | | | | | | | | |
| 013 | 12 | | PA | | 11-0 | 23-34-18 | D04709P | 27 | | | D05191P | 4 | | | ALL |
| 014 | 16 | | PA | | 24-0 | 23-34-15 | SP00143 | | S | | D05191P | 6 | | | 050-099 |
| 014 | 16 | | PA | | 24-0 | 23-34-15 | SP00143 | | 9 | | D05191P | 6 | | | 150-199, 275-299 |
| 015 | 12 | | PA | | 24-0 | 23-34-18 | SP00053 | | S | | D05191P | 5 | | | 050-099 |
| 015 | 12 | | PA | | 24-0 | 23-34-18 | SP00053 | | 9 | | D05191P | 5 | | | 150-199, 275-299 |
| 016 | 16 | | PA | | 16-0 | 23-34-16 | SP00139 | | S | | D05191P | 7 | | | 050-099 |
| 016 | 16 | | PA | | 16-0 | 23-34-16 | SP00139 | | 9 | | D05191P | 7 | | | 150-199, 275-299 |
| 017 | 22 | | PA | | 24-0 | 23-71-11 | D04709P | 9 | | | D05029J | 9 | | | 050-099 |
| 017 | 22 | | PA | | 23-0 | 23-71-11 | D04709P | 9 | | | D05029J | 9 | | | 150-199, 275-299 |
| 018 | 22 | | PA | | 24-0 | 23-71-11 | D04709P | 10 | | | D05029J | 10 | | | 050-099 |
| 018 | 22 | | PA | | 23-0 | 23-71-11 | D04709P | 10 | | | D05029J | 10 | | | 150-199, 275-299 |
| 019 | 12 | | PA | | 24-0 | 23-34-18 | SP00057 | | S | | D05191P | 8 | | | 050-099 |
| 019 | 12 | | PA | | 24-0 | 23-34-18 | SP00057 | | 9 | | D05191P | 8 | | | 150-199, 275-299 |
| 020 | 20 | | PA | | 30-0 | SPARE | D05029J | 12 | | | D05193P | 12 | | | ALL |
| 021 | 20 | | PA | | 24-0 | SPARE | D05029J | 11 | | | D04709P | 11 | | | 050-099 |
| 021 | 20 | | PA | | 23-0 | SPARE | D05029J | 11 | | | D04709P | 11 | | | 150-199, 275-299 |
| 022 | 22 | | PA | | 24-0 | SPARE | D05029J | 13 | | | D04709P | 7 | | | 050-099 |
| 022 | 22 | | PA | | 23-0 | SPARE | D05029J | 13 | | | D04709P | 7 | | | 150-199, 275-299 |
| 024 | 24 | | PK | | 23-0 | 23-12-11 | D05029J | 6 | | | D04709P | 8 | | | 050-099 |
| 024 | 24 | | PK | | 23-0 | 23-12-11 | D04709P | 8 | | | D05029J | 16 | | | 150-199, 275-299 |
| 025 | 22 | | PA | | 11-0 | SPARE | D05193P | 11 | | | D04709P | 13 | | | 050-099 |
| 025 | 22 | | PA | | 11-0 | 30-21-11 | D05193P | 5 | | | D04709P | 13 | | | 150-154 |
| 025 | 22 | | PA | | 11-0 | SPARE | D05193P | 5 | | | D04709P | 13 | | | 155-199, 275-299 |
| 026 | 24 | | PK | | 30-0 | 23-34-12 | D05029J | 14 | | | D05193P | 8 | | | 050-099 |
| 026 | 24 | | PK | | 30-0 | 23-34-12 | D05193P | 8 | | | D05029J | 14 | | | 150-199, 275-299 |
| 027 | 24 | | PK | | 30-0 | 23-34-12 | D05029J | 15 | | | D05193P | 7 | | | 050-099 |
| 027 | 24 | | PK | | 30-0 | 23-34-12 | D05193P | 7 | | | D05029J | 15 | | | 150-199, 275-299 |
| 028 | 24 | | PK | | 30-0 | 23-34-12 | D05029J | 5 | | | D05193P | 5 | | | 050-099 |
| 028 | 24 | | PK | | 30-0 | 23-34-12 | D05193P | 6 | | | D05029J | 6 | | | 150-199, 275-299 |
| 029 | 22 | | PA | | 18-0 | 23-31-12 | SP00399 | | 9 | | D04709P | 12 | | | ALL |
| 030 | 24 | | PK | | 11-0 | 30-21-11 | D04709P | 14 | | | D05193P | 9 | | | 050-099, 155-199 |
| 035 | 20 | | UA | | 6-0 | 78-34-11 | D04709P | | | FA | GD00670 | S.. | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 035 | 20 | | UA | | 5-0 | 78-34-11 | D04709P | | | FA | GD00670 | S.. | 2 | | 157, 167-199, 277-299 |
| 036 | 18 | | PQ | BK | 20-0 | 78-34-11 | D04709P | 22 | DL | | D05193P | 22 | DK | | ALL |
| 036Z | | | | BK | 0-0 | 78-34-11 | D04709P | | | FA | D05193P | | | FB | ALL |
| 037 | 18 | | PQ | BL | 20-0 | 78-34-11 | D04709P | 25 | DL | | D05193P | 17 | DK | | ALL |
| 037Z | | | | BL | 0-0 | 78-34-11 | D04709P | | | FA | D05193P | | | FB | ALL |
| 038 | 18 | | PQ | BM | 20-0 | 78-34-11 | D04709P | 26 | DL | | D05193P | 14 | DK | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0680

Page 8

Mar 14/2007



| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | | |
| W0689 | 286T0689 | | | E2-5 TO P36 & P33 (continued) | | | | | | | | | | | |
| 038Z | | | | BM | 0-0 | 78-34-11 | D04709P | | | FA | D05193P | | | FB | ALL |
| 039 | 18 | | PQ | BN | 20-0 | 78-34-11 | D04709P | 28 | DL | | D05193P | 13 | DK | | ALL |
| 039Z | | | | BN | 0-0 | 78-34-11 | D04709P | | | FA | D05193P | | | FB | ALL |
| 040 | 24 | | PK | | 65-0 | 78-36-11 | D05193P | 18 | | | D04709P | 18 | | | ALL |
| 041 | 24 | | PK | | 65-0 | 78-36-11 | D05193P | 19 | | | D04709P | 17 | | | ALL |
| 042 | 24 | | PK | | 65-0 | 78-36-11 | D05193P | 20 | | | D04709P | 16 | | | ALL |
| FRA | | | | | 0-0 | 78-34-11 | D04709P | 21 | | | D04709P | | | FA | ALL |
| FRB | | | | | 0-0 | 78-34-11 | D05193P | 15 | | | D05193P | | | FB | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0690 | 286T0690 | | | LEFT MAIN GEAR UPPER J-BOX-SYS 2 | | | | | | | | | | | |
| 201B | 18 | UB | B | 18-0 | 32-61-11 | D04318P | | 2 | | D05024P | | 2 | | 050-099 | |
| 201B | 18 | UB | B | 17-4 | 32-61-11 | D04318P | | 2 | | D05024P | | 2 | | 150-199, 275-299 | |
| 201R | 18 | UB | B | 0-0 | 32-61-11 | D04318P | | 1 | | D05024P | | 1 | | ALL | |
| 202B | 18 | UB | C | 18-0 | 32-61-11 | D04318P | | 4 | | D05024P | | 4 | | 050-099 | |
| 202B | 18 | UB | C | 17-4 | 32-61-11 | D04318P | | 4 | | D05024P | | 4 | | 150-199, 275-299 | |
| 202R | 18 | UB | C | 0-0 | 32-61-11 | D04318P | | 3 | | D05024P | | 3 | | ALL | |
| 203B | 18 | UB | A | 18-0 | 32-09-12 | D04318P | | 6 | | D05024P | | 6 | | 050-099 | |
| 203B | 18 | UB | A | 17-4 | 32-09-12 | D04318P | | 6 | | D05024P | | 6 | | 150-199, 275-299 | |
| 203R | 18 | UB | A | 0-0 | 32-09-12 | D04318P | | 5 | | D05024P | | 5 | | ALL | |
| 204B | 20 | VG | D | 18-0 | 32-42-11 | D04318P | | 8 | | D05024P | | 12 | | 050-099 | |
| 204B | 20 | VG | D | 17-4 | 32-42-11 | D04318P | | 8 | | D05024P | | 12 | | 150-199, 275-299 | |
| 204R | 20 | VG | D | 0-0 | 32-42-11 | D04318P | | 7 | | D05024P | | 11 | | ALL | |
| 204Z | | | D | 0-0 | 32-42-11 | D04318P | | 15 | | D05024P | | 15 | | ALL | |
| 205B | 20 | VG | E | 18-0 | 32-42-11 | D04318P | | 10 | | D05024P | | 14 | | 050-099 | |
| 205B | 20 | VG | E | 17-4 | 32-42-11 | D04318P | | 10 | | D05024P | | 14 | | 150-199, 275-299 | |
| 205R | 20 | VG | E | 0-0 | 32-42-11 | D04318P | | 9 | | D05024P | | 13 | | ALL | |
| 205Z | | | E | 0-0 | 32-42-11 | D04318P | | 16 | | D05024P | | 16 | | ALL | |
| 207B | 20 | VG | K | 20-0 | 32-45-13 | D08268P | | 8 | | D05024P | | 25 | | 050-099 | |
| 207B | 20 | VG | K | 19-9 | 32-45-13 | D08268P | | 8 | | D05024P | CAP | Y | | 150-154 | |
| 207B | 20 | VG | K | 19-9 | 32-45-13 | D08268P | | 8 | | D05024P | | 25 | | 155-199, 275-299 | |
| 207R | 20 | VG | K | 0-0 | 32-45-13 | D08268P | | 9 | | D05024P | | 26 | | 050-099, 155-199, 275-299 | |
| 207R | 20 | VG | K | 0-0 | 32-45-13 | D08268P | | 9 | | D05024P | CAP | Y | | 150-154 | |
| 207Z | | | K | 0-0 | 32-45-13 | D08268P | | 10 | | D05024P | | 27 | | 050-099, 155-199, 277-299 | |
| 207Z | | | K | 0-0 | 32-45-13 | D08268P | | 10 | | D05024P | DED | | | 150-154, 275-276 | |
| 208B | 20 | VG | L | 20-0 | 32-45-13 | D08268P | | 11 | | D05024P | | 28 | | 050-099 | |
| 208B | 20 | VG | L | 19-9 | 32-45-13 | D08268P | | 11 | | D05024P | CAP | Y | | 150-154 | |
| 208B | 20 | VG | L | 19-9 | 32-45-13 | D08268P | | 11 | | D05024P | | 28 | | 155-199, 275-299 | |
| 208R | 20 | VG | L | 0-0 | 32-45-13 | D08268P | | 12 | | D05024P | | 29 | | 050-099, 155-199, 275-299 | |
| 208R | 20 | VG | L | 0-0 | 32-45-13 | D08268P | | 12 | | D05024P | CAP | Y | | 150-154 | |
| 208Z | | | L | 0-0 | 32-45-13 | D08268P | | 13 | | D05024P | | 30 | | 050-099, 155-199, 277-299 | |
| 208Z | | | L | 0-0 | 32-45-13 | D08268P | | 13 | | D05024P | DED | | | 150-154, 275-276 | |
| 451G | 18 | UY | F | 18-0 | 32-46-11 | D04318P | | 12 | 4G | D05024P | | 8 | 4H | 050-099 | |
| 451G | 18 | UY | F | 17-4 | 32-46-11 | D04318P | | 12 | 4G | D05024P | | 8 | 4H | 150-199, 275-299 | |
| 451W | 18 | UY | F | 0-0 | 32-46-11 | D04318P | | 11 | 4K | D05024P | | 7 | 4L | ALL | |
| 452G | 18 | UY | G | 18-0 | 32-46-11 | D04318P | | 14 | 4G | D05024P | | 10 | 4H | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0690

Page 1

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0690 | 286T0690 | | | LEFT MAIN GEAR UPPER J-BOX-SYS 2 (continued) | | | | | | | | | | | | | |
| 452G | 18 | | UY | G | 17-4 | 32-46-11 | D04318P | 14 | 4G | | | | D05024P | 10 | 4H | | 150-199, 275-299 |
| 452W | 18 | | UY | G | 0-0 | 32-46-11 | D04318P | 13 | 4K | | | | D05024P | 9 | 4L | | ALL |
| W0691 | 286T0691 | | | E2-3 TO P61 RIGHT SIDE PNL | | | | | | | | | | | | | |
| 001 | 22 | | PA | | 20-10 | 31-31-11 | D04725J | 1 | | | | | D04707P | 1 | | | ALL |
| 002 | 22 | | PA | | 20-10 | 31-31-11 | D04725J | 2 | | | | | D04707P | 2 | | | ALL |
| 005 | 24 | | PK | | 20-10 | 31-31-11 | D04725J | 5 | | | | | D04707P | 5 | | | ALL |
| 006 | 24 | | PK | | 20-10 | 31-31-11 | D04725J | 6 | | | | | D04707P | 6 | | | ALL |
| 010 | 24 | | PK | | 20-10 | 31-31-11 | D04707P | 21 | | | | | D04725J | 21 | | | 050-099 |
| 010 | 24 | | PK | | 20-10 | 31-31-11 | D04725J | 21 | | | | | D04707P | 21 | | | 150-199, 275-299 |
| 011 | 22 | | PA | | 20-10 | 31-31-11 | D04707P | 22 | | | | | D04725J | 22 | | | 050-099 |
| 011 | 22 | | PA | | 20-10 | 31-31-11 | D04725J | 22 | | | | | D04707P | 22 | | | 150-199, 275-299 |
| 012 | 24 | | PK | | 20-10 | SPARE | D04725J | 23 | | | | | D04707P | 23 | | | 050-099, 150-199 |
| 013 | 24 | | PK | | 20-10 | SPARE | D04725J | 24 | | | | | D04707P | 24 | | | 050-099, 150-199 |
| 014 | 22 | | PA | | 20-10 | SPARE | D04725J | | CAP | Y | | | D04707P | CAP | Y | | ALL |
| 015 | 22 | | PA | | 20-10 | SPARE | D04725J | | CAP | Y | | | D04707P | CAP | Y | | ALL |
| 016 | 24 | | PK | | 20-10 | SPARE | D04707P | 31 | | | | | D04725J | 31 | | | 050-099 |
| 016 | 24 | | PK | | 20-10 | SPARE | D04725J | 31 | | | | | D04707P | 31 | | | 150-199, 275-299 |
| 017 | 24 | | PK | | 20-10 | 31-31-11 | D04725J | 25 | | | | | D04707P | 25 | | | ALL |
| 018 | 24 | | PK | | 20-10 | SPARE | D04725J | | CAP | Y | | | D04707P | CAP | Y | | ALL |
| 019 | 22 | | PA | | 20-10 | SPARE | D04725J | 27 | | | | | D04707P | 27 | | | ALL |
| 026 | 22 | | PA | | 20-10 | 31-35-11 | D04725J | 28 | | | | | D04707P | 28 | | | ALL |
| 027 | 24 | | PV | BB | 20-10 | SPARE | D04725J | 46 | | | | | D04707P | 46 | | | 150-199 |
| 027F | 20 | | UA | | 1-6 | SPARE | D04707P | | | | FD | | GD00735 | S.. | E | | 150-154 |
| 027F | 20 | | UA | | 1-6 | SPARE | D04707P | | | | FD | | GD00735 | S.. | = | | 155-199 |
| 027Z | | | | BB | 0-0 | SPARE | D04725J | | | | FC | | D04707P | | | FD | 150-199 |
| 028 | 24 | | PV | BC | 20-10 | SPARE | D04725J | 47 | | | | | D04707P | 47 | | | 150-199 |
| 028Z | | | | BC | 0-0 | SPARE | D04725J | | | | FC | | D04707P | | | FD | 150-199 |
| 029 | 24 | | PV | BD | 20-10 | SPARE | D04725J | 48 | | | | | D04707P | 48 | | | 150-199 |
| 029Z | | | | BD | 0-0 | SPARE | D04725J | | | | FC | | D04707P | | | FD | 150-199 |
| 030 | 24 | | PK | | 20-10 | SPARE | D04725J | 53 | | | | | D04707P | 53 | | | 150-199 |
| 031 | 24 | | PK | | 20-10 | SPARE | D04725J | 54 | | | | | D04707P | 54 | | | 150-199 |
| 032 | 24 | | PK | | 20-10 | 31-31-22 | D04707P | 49 | | | | | D04725J | 49 | | | ALL |
| 033 | 24 | | PK | | 20-10 | 31-31-22 | D04707P | 55 | | | | | D04725J | 55 | | | ALL |
| 038 | 24 | | PK | | 20-10 | SPARE | D04725J | 3 | | | | | D04707P | 3 | | | 150-199, 275-299 |
| 057 | 22 | | PA | | 19-4 | SPARE | D06225P | 1 | | | | | D06223J | 1 | | | 050-099 |
| 058 | 24 | | PK | | 19-4 | 34-61-15 | D06225P | 2 | | | | | D06223J | 2 | | | ALL |
| 059 | 24 | | PK | | 19-4 | 34-61-15 | D06225P | 3 | | | | | D06223J | 3 | | | ALL |
| 060 | 24 | | PK | | 19-4 | 34-61-15 | D06225P | 10 | | | | | D06223J | 10 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0690

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0691 | 286T0691 | | | E2-3 TO P61 RIGHT SIDE PNL (continued) | | | | | | | | | | | |
| 061 | 24 | | PK | 19-4 | 34-61-15 | D06225P | 11 | | | D06223J | 11 | | | ALL | |
| 062 | 24 | | PK | 20-10 | 34-61-24 | D04707P | 8 | | | D04725J | 13 | | | 050-099, 155-199, 276-299 | |
| 202 | 20 | | UA | 1-6 | 31-31-11 | D04707P | | | IB | GD00739 | S.. | E | | ALL | |
| 202B | 24 | | PW | 20-10 | 31-31-11 | D04725J | 11 | | | D04707P | 11 | | | ALL | |
| 202R | 24 | | PW | 0-0 | 31-31-11 | D04725J | 10 | | | D04707P | 10 | | | ALL | |
| 202Z | | | IB | 0-0 | 31-31-11 | D04725J | 26 | | | D04707P | | | IB | ALL | |
| 204 | 20 | | UA | 1-6 | 31-31-11 | D04707P | | | ID | GD00739 | S.. | E | | ALL | |
| 204B | 24 | | PW | 20-10 | 31-31-11 | D04725J | 15 | | | D04707P | 15 | | | ALL | |
| 204R | 24 | | PW | 0-0 | 31-31-11 | D04725J | 14 | | | D04707P | 14 | | | ALL | |
| 204Z | | | ID | 0-0 | 31-31-11 | D04725J | 29 | | | D04707P | | | ID | ALL | |
| 205 | 20 | | UA | 1-6 | 31-31-11 | D04707P | | | IE | GD00739 | S.. | E | | ALL | |
| 205B | 24 | | PW | 20-10 | 31-31-11 | D04725J | 17 | | | D04707P | 17 | | | ALL | |
| 205R | 24 | | PW | 0-0 | 31-31-11 | D04725J | 16 | | | D04707P | 16 | | | ALL | |
| 205Z | | | IE | 0-0 | 31-31-11 | D04725J | 30 | | | D04707P | | | IE | ALL | |
| 206 | 20 | | UA | 1-6 | 31-31-11 | D04707P | | | IF | GD00739 | S.. | E | | ALL | |
| 206B | 24 | | PW | 20-10 | 31-31-11 | D04725J | 36 | | | D04707P | 36 | | | ALL | |
| 206R | 24 | | PW | 0-0 | 31-31-11 | D04725J | 35 | | | D04707P | 35 | | | ALL | |
| 206Z | | | IF | 0-0 | 31-31-11 | D04725J | 7 | | | D04707P | | | IF | ALL | |
| 207 | 20 | | UA | 1-6 | SPARE | D04707P | | | IG | GD00735 | S.. | E | | 275-299 | |
| 207B | 24 | | PW | 20-10 | SPARE | D04725J | 43 | | | D04707P | 43 | | | 275-299 | |
| 207R | 24 | | PW | 0-0 | SPARE | D04725J | 42 | | | D04707P | 42 | | | 275-299 | |
| 207Z | | | IG | 0-0 | SPARE | D04725J | 44 | | | D04707P | | | IG | 275-299 | |
| 208 | 20 | | UA | 1-6 | 31-35-11 | D04707P | | | IH | GD00735 | S.. | E | | ALL | |
| 208B | 24 | | PW | 20-10 | 31-35-11 | D04725J | 52 | | | D04707P | 52 | | | ALL | |
| 208R | 24 | | PW | 0-0 | 31-35-11 | D04725J | 51 | | | D04707P | 51 | | | ALL | |
| 208Z | | | IH | 0-0 | 31-35-11 | D04725J | 50 | | | D04707P | | | IH | ALL | |
| 212 | 20 | | UA | 1-6 | 34-61-15 | D06225P | REF | | IL | GD00735 | S.. | E | | 050-099 | |
| 212 | 20 | | UA | 1-6 | 34-61-15 | D06225P | | | IL | GD00735 | S.. | E | *1 | 150-154 | |
| 212 | 20 | | UA | 1-6 | 34-61-15 | D06225P | | | IL | GD00735 | S.. | E | | 155-199, 275-299 | |
| 212B | 24 | | PW | 19-4 | 34-61-15 | D06225P | 5 | | | D06223J | 5 | | | ALL | |
| 212F | 20 | | UA | 0-7 | 34-61-15 | D06225P | 6 | | | D06225P | REF | | IL | 050-099 | |
| 212F | 20 | | UA | 0-7 | 34-61-15 | D06225P | 6 | | | D06225P | | | IL | 150-199, 275-299 | |
| 212R | 24 | | PW | 0-0 | 34-61-15 | D06225P | 4 | | | D06223J | 4 | | | ALL | |
| 212Z | | | IL | 0-0 | 34-61-15 | D06225P | REF | | IL | D06223J | 6 | | | 050-099 | |
| 212Z | | | IL | 0-0 | 34-61-15 | D06225P | | | IL | D06223J | 6 | | | 150-199, 275-299 | |
| 213 | 20 | | UA | 1-6 | 34-61-15 | D06225P | REF | | IM | GD00735 | S.. | E | | 050-099 | |
| 213 | 20 | | UA | 1-6 | 34-61-15 | D06225P | | | IM | GD00735 | S.. | E | *1 | 150-154 | |
| 213 | 20 | | UA | 1-6 | 34-61-15 | D06225P | | | IM | GD00735 | S.. | E | | 155-199, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W0690
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|--|----|-------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0691 | 286T0691 | E2-3 TO P61 RIGHT SIDE PNL (continued) | | | | | | | | | | | | | | | |
| 213B | 24 | PW | IM | 19-4 | 34-61-15 | D06225P | | 8 | | | | | D06223J | 8 | | | ALL |
| 213F | 20 | UA | | 0-7 | 34-61-15 | D06225P | | 9 | | | | | D06225P | REF | | IM | 050-099 |
| 213F | 20 | UA | | 0-7 | 34-61-15 | D06225P | | 9 | | | | | D06225P | | | IM | 150-199, 275-299 |
| 213R | 24 | PW | IM | 0-0 | 34-61-15 | D06225P | | 7 | | | | | D06223J | 7 | | | ALL |
| 213Z | | | IM | 0-0 | 34-61-15 | D06225P | | | REF | | IM | | D06223J | 9 | | | 050-099 |
| 213Z | | | IM | 0-0 | 34-61-15 | D06225P | | | | | IM | | D06223J | 9 | | | 150-199, 275-299 |
| 214 | 20 | UA | | 1-6 | 34-61-15 | D06225P | | | | | IN | | GD00735 | S.. | E | | ALL |
| 214B | 24 | PW | IN | 19-4 | 34-61-15 | D06225P | | 13 | | | | | D06223J | 13 | | | ALL |
| 214F | 20 | UA | | 0-7 | 34-61-15 | D06225P | | 14 | | | | | D06225P | | | IN | ALL |
| 214R | 24 | PW | IN | 0-0 | 34-61-15 | D06225P | | 12 | | | | | D06223J | 12 | | | ALL |
| 214Z | | | IN | 0-0 | 34-61-15 | D06225P | | | | | IN | | D06223J | 14 | | | ALL |
| 301B | 24 | PX | MA | 20-10 | 31-31-19 | D04725J | | 38 | | | | | D04707P | 38 | | | ALL |
| 301R | 24 | PX | MA | 0-0 | 31-31-19 | D04725J | | 37 | | | | | D04707P | 37 | | | ALL |
| 301Y | 24 | PX | MA | 0-0 | 31-31-19 | D04725J | | 39 | | | | | D04707P | 39 | | | ALL |
| 301Z | | | MA | 0-0 | 31-31-19 | D04725J | | 40 | | | | | D04707P | 40 | | | ALL |
| FRB | | | | 0-0 | 31-31-11 | D04707P | | 7 | | | | | D04707P | | | IB | ALL |
| FRC | | | | 0-0 | SPARE | D04725J | | | | | FC | | D04725J | 45 | | | 150-199 |
| FRD | | | | 0-0 | SPARE | D04707P | | | | | FD | | D04707P | 45 | | | 150-199 |
| FRE | | | | 0-0 | 31-31-11 | D04707P | | | | | IE | | D04707P | 18 | | | ALL |
| FRF | | | | 0-0 | 31-31-11 | D04707P | | | | | IF | | D04707P | 19 | | | ALL |
| FRG | | | | 0-0 | SPARE | D04707P | | | | | IG | | D04707P | 44 | | | 275-299 |
| FRH | | | | 0-0 | 31-35-11 | D04707P | | | | | IH | | D04707P | 50 | | | ALL |
| FRI | | | | 0-0 | 31-31-11 | D04707P | | | | | ID | | D04707P | 13 | | | ALL |
| W0692 | 286T0692 | FWD CARGO COMPARTMENTS MOKE DET AIR FLOW BLOWER 2 | | | | | | | | | | | | | | | |
| 001 | 20 | PA | | 2-0 | 26-16-21 | D01138 | | 1 | | | | | D06948J | 1 | | | ALL |
| 002 | 20 | PA | | 2-0 | 26-16-21 | D01138 | | 2 | | | | | D06948J | 2 | | | ALL |
| 003 | 20 | PA | | 2-0 | 26-16-21 | D01138 | | 3 | | | | | D06948J | 3 | | | ALL |
| W0693 | 286T0693 | E2-3 TO LEFT MAIN W/W AREA | | | | | | | | | | | | | | | |
| 004 | 20 | PA | | 73-0 | SPARE | D04727J | | 10 | | | | | D04729J | 10 | | | 050-099 |
| 004 | 20 | PA | | 82-0 | SPARE | D04727J | | 10 | | | | | D04729J | 10 | | | 150-199, 275-299 |
| 201B | 24 | PW | IA | 73-0 | 31-31-13 | D04727J | | 5 | | | | | D04729J | 5 | | | 050-099 |
| 201B | 24 | PW | IA | 82-0 | 31-31-13 | D04727J | | 5 | | | | | D04729J | 5 | | | 150-199, 275-299 |
| 201R | 24 | PW | IA | 0-0 | 31-31-13 | D04727J | | 4 | | | | | D04729J | 4 | | | ALL |
| 201Z | | | IA | 0-0 | 31-31-13 | D04727J | | | | | FA | | D04729J | | | FB | ALL |
| 202B | 24 | PW | IB | 73-0 | 31-31-13 | D04727J | | 7 | | | | | D04729J | 7 | | | 050-099 |
| 202B | 24 | PW | IB | 82-0 | 31-31-13 | D04727J | | 7 | | | | | D04729J | 7 | | | 150-199, 275-299 |
| 202R | 24 | PW | IB | 0-0 | 31-31-13 | D04727J | | 6 | | | | | D04729J | 6 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0690

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0693 | 286T0693 | | | E2-3 TO LEFT MAIN W/W AREA (continued) | | | | | | | | | | | |
| 202Z | | | | IB | 0-0 | 31-31-13 | D04727J | | | FA | D04729J | | | FB | ALL |
| 203B | 24 | PW | | IC | 73-0 | 31-31-13 | D04727J | 9 | | | D04729J | 9 | | | 050-099 |
| 203B | 24 | PW | | IC | 82-0 | 31-31-13 | D04727J | 9 | | | D04729J | 9 | | | 150-199, 275-299 |
| 203R | 24 | PW | | IC | 0-0 | 31-31-13 | D04727J | 8 | | | D04729J | 8 | | | ALL |
| 203Z | | | | IC | 0-0 | 31-31-13 | D04727J | | | FA | D04729J | | | FB | ALL |
| 204B | 24 | PL | | ID | 73-0 | 31-31-13 | D04727J | 2 | | | D04729J | 2 | | | 050-099 |
| 204B | 24 | PL | | ID | 82-0 | 31-31-13 | D04727J | 2 | | | D04729J | 2 | | | 150-199, 275-299 |
| 204R | 24 | PL | | ID | 0-0 | 31-31-13 | D04727J | 1 | | | D04729J | 1 | | | ALL |
| FRA | | | | | 0-0 | 31-31-13 | D04727J | | | FA | D04727J | 3 | | | ALL |
| FRB | | | | | 0-0 | 31-31-13 | D04729J | | | FB | D04729J | 3 | | | ALL |
| W0694 | 286T0694 | | | AFT CARGO COMPARTMENT SMOKE DET AIR FLOW BLOWER 2 | | | | | | | | | | | |
| 001 | 20 | PA | | | 2-0 | 26-16-21 | D01142 | 1 | | | D06950J | 1 | | | ALL |
| 002 | 20 | PA | | | 2-0 | 26-16-21 | D01142 | 2 | | | D06950J | 2 | | | ALL |
| 003 | 20 | PA | | | 2-0 | 26-16-21 | D01142 | 3 | | | D06950J | 3 | | | ALL |
| W0695 | 286T0695 | | | E2-3 TO POSITION XDCR | | | | | | | | | | | |
| 001 | 22 | PA | | | 32-0 | 31-31-15 | D04731J | 1 | | | D01685 | 1 | | | ALL |
| 002 | 22 | PA | | | 21-0 | 31-31-15 | D04731J | 2 | | | D01687 | 1 | | | ALL |
| 003 | 22 | PA | | | 23-0 | 31-31-15 | D04731J | 3 | | | D01689 | 1 | | | ALL |
| 004 | 20 | PA | | | 2-0 | 31-31-15 | GD00643 | A.. | E | | D01685 | 4 | | | 050-099, 150-156, 162-166, 275-276 |
| 005 | 20 | PA | | | 2-0 | 31-31-15 | GD00643 | A.. | E | | D01685 | 5 | | | ALL |
| 006 | 20 | PA | | | 2-0 | 31-31-15 | GD00645 | A.. | E | | D01687 | 4 | | | ALL |
| 007 | 20 | PA | | | 2-0 | 31-31-15 | GD00645 | A.. | E | | D01687 | 5 | | | ALL |
| 008 | 20 | PA | | | 2-0 | 31-31-15 | GD00647 | A.. | E | | D01689 | 4 | | | 050-099, 150-156, 162-166, 275-276 |
| 009 | 20 | PA | | | 2-0 | 31-31-15 | GD00647 | A.. | E | | D01689 | 5 | | | ALL |
| 010 | 22 | PA | | | 12-0 | 31-31-15 | D01635 | A | | | D04731J | 10 | | | ALL |
| 011 | 20 | PA | | | 3-0 | 31-31-15 | D01635 | E | | | GD00687 | S.. | E | | ALL |
| 012 | 20 | PA | | | 3-0 | 31-31-15 | D01635 | B | | | GD00689 | D.. | E | | ALL |
| 201B | 24 | PL | IA | | 32-0 | 31-31-15 | D04731J | 5 | | | D01685 | 3 | | | 050-099, 150-156, 162-166, 275-276 |
| 201R | 24 | PL | IA | | 0-0 | 31-31-15 | D04731J | 4 | | | D01685 | 2 | | | 050-099, 150-156, 162-166, 275-276 |
| 202B | 24 | PL | IB | | 21-0 | 31-31-15 | D04731J | 7 | | | D01687 | 3 | | | ALL |
| 202R | 24 | PL | IB | | 0-0 | 31-31-15 | D04731J | 6 | | | D01687 | 2 | | | ALL |
| 203B | 24 | PL | IC | | 23-0 | 31-31-15 | D04731J | 9 | | | D01689 | 3 | | | 050-099, 150-156, 162-166, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0690

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0695 | 286T0695 | | | E2-3 TO POSITION XDCR (continued) | | | | | | | | | | | |
| 203R | 24 | PL | IC | | 0-0 | 31-31-15 | D04731J | 8 | | | D01689 | 2 | | | 050-099, 150-156, 162-166, 275-276 |
| 204 | 20 | UA | | | 3-0 | 31-31-15 | D01635 | | | ID | GD00687 | S.. | E | | 050-099 |
| 204 | 20 | UA | | | 2-0 | 31-31-15 | D01635 | | | ID | GD00687 | S.. | E | | 150-199, 275-299 |
| 204B | 24 | PW | ID | | 12-0 | 31-31-15 | D01635 | | D | | D04731J | 12 | | | ALL |
| 204R | 24 | PW | ID | | 0-0 | 31-31-15 | D01635 | | C | | D04731J | 11 | | | ALL |
| 204Z | | | ID | | 0-0 | 31-31-15 | D01635 | | | ID | D04731J | 13 | | | ALL |
| 301B | 24 | PM | MA | | 33-0 | 31-31-15 | D04731J | 5 | | | D01685 | 3 | | | 157, 167-199, 277-299 |
| 301R | 24 | PM | MA | | 0-0 | 31-31-15 | D04731J | 4 | | | D01685 | 2 | | | 157, 167-199, 277-299 |
| 301Y | 24 | PM | MA | | 0-0 | 31-31-15 | D04731J | 17 | | | D01685 | 4 | | | 157, 167-199, 277-299 |
| 302B | 24 | PM | MB | | 23-0 | 31-31-15 | D04731J | 9 | | | D01689 | 3 | | | 157, 167-199, 277-299 |
| 302R | 24 | PM | MB | | 0-0 | 31-31-15 | D04731J | 8 | | | D01689 | 2 | | | 157, 167-199, 277-299 |
| 302Y | 24 | PM | MB | | 0-0 | 31-31-15 | D04731J | 18 | | | D01689 | 4 | | | 157, 167-199, 277-299 |
| W0697 | 286T0697 | | | TMC,STAB. & FLAP POS MODULE,P50 TO SHELF | | | | | | | | | | | |
| 001 | 22 | PA | | | 26-0 | 22-24-11 | D04367J | 1 | | | D05277P | 1 | | | ALL |
| 006 | 22 | PA | | | 26-0 | 27-61-11 | D04367J | 16 | | | D05277P | 16 | | | ALL |
| 008 | 24 | PK | | | 26-0 | 22-32-13 | D04367J | 8 | | | D05277P | 8 | | | ALL |
| 009 | 24 | PK | | | 26-0 | 22-32-13 | D04367J | 9 | | | D05277P | 9 | | | ALL |
| 010 | 24 | PK | | | 26-0 | 22-32-13 | D04367J | 10 | | | D05277P | 10 | | | ALL |
| 011 | 24 | PK | | | 26-0 | 22-32-13 | D04367J | 11 | | | D05277P | 11 | | | ALL |
| 012 | 24 | PK | | | 26-0 | 22-32-13 | D04367J | 12 | | | D05277P | 12 | | | ALL |
| 018 | 22 | PA | | | 26-0 | SPARE | D04367J | 18 | | | D05277P | 18 | | | ALL |
| 019 | 22 | PA | | | 26-0 | SPARE | D04367J | 19 | | | D05277P | 19 | | | ALL |
| 020 | 22 | PA | | | 26-0 | 27-41-11 | D04367J | 15 | | | D05277P | 15 | | | ALL |
| 022 | 24 | PK | | | 26-0 | 22-12-11 | D04367J | 22 | | | D05277P | 22 | | | ALL |
| 023 | 24 | PK | | | 26-0 | 22-12-11 | D04367J | 23 | | | D05277P | 23 | | | ALL |
| 024 | 24 | PK | | | 26-0 | 22-12-11 | D04367J | 24 | | | D05277P | 24 | | | ALL |
| 025 | 24 | PK | | | 26-0 | 22-12-11 | D04367J | 25 | | | D05277P | 25 | | | ALL |
| 028 | 24 | PK | | | 26-0 | 34-46-12 | D04367J | 28 | | | D05277P | 28 | | | ALL |
| 035 | 24 | PK | | | 26-0 | SPARE | D04367J | 35 | | | D05277P | 35 | | | ALL |
| 036 | 24 | PK | | | 26-0 | SPARE | D04367J | 36 | | | D05277P | 36 | | | ALL |
| 201B | 22 | PB | IA | | 26-0 | 27-41-11 | D04367J | 5 | | | D05277P | 5 | | | ALL |
| 201R | 22 | PB | IA | | 0-0 | 27-41-11 | D04367J | 4 | | | D05277P | 4 | | | ALL |
| 202B | 24 | PL | IB | | 26-0 | 22-32-13 | D04367J | 21 | | | D05277P | 21 | | | ALL |
| 202R | 24 | PL | IB | | 0-0 | 22-32-13 | D04367J | 20 | | | D05277P | 20 | | | ALL |
| 205B | 24 | PL | IE | | 26-0 | 27-58-21 | D04367J | 32 | | | D05277P | 32 | | | ALL |
| 205R | 24 | PL | IE | | 0-0 | 27-58-21 | D04367J | 33 | | | D05277P | 33 | | | ALL |
| 206B | 24 | PL | IF | | 26-0 | SPARE | D04367J | 26 | | | D05277P | 26 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0690

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|---|-------|----------|-------------|------|------|-----------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0697 | 286T0697 | | | TMC,STAB. & FLAP POS MODULE,P50 TO SHELF (continued) | | | | | | | | | | | |
| 206R | 24 | PL | IF | | 0-0 | SPARE | D04367J | | 27 | | D05277P | | 27 | | ALL |
| 301B | 24 | PM | MA | | 26-0 | 27-58-21 | D04367J | | 29 | | D05277P | | 29 | | ALL |
| 301R | 24 | PM | MA | | 0-0 | 27-58-21 | D04367J | | 30 | | D05277P | | 30 | | ALL |
| 301Y | 24 | PM | MA | | 0-0 | 27-58-21 | D04367J | | 31 | | D05277P | | 31 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0690
Page 7 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0700 | 286T0700 | | | FWD CARGO LOADING CONTROL (P24) | | | | | | | | | | | | | |
| 001 | 20 | | PA | 5-0 | 25-53-11 | D05216P | | | | 1 | | | D00820 | 1 | | | 050-099 |
| 001 | 20 | | PA | 7-0 | 25-53-11 | D05216P | | | | 1 | | | D00820 | 1 | | | 150-199, 275-299 |
| 002 | 20 | | PA | 5-0 | 25-53-11 | D05216P | | | | 2 | | | D00820 | 2 | | | 050-099 |
| 002 | 20 | | PA | 7-0 | 25-53-11 | D05216P | | | | 2 | | | D00820 | 2 | | | 150-199, 275-299 |
| 003 | 20 | | PA | 7-0 | 25-53-11 | D05216P | | | | 3 | | | SP00764 | | 1A | | 050-099 |
| 003 | 20 | | PA | 8-0 | 25-53-11 | D05216P | | | | 3 | | | SP00764 | | 1A | | 150-199, 275-299 |
| 004 | 20 | | PA | 5-0 | 25-53-13 | D05216P | | | | 4 | | | D00820 | 4 | | | 050-099 |
| 004 | 20 | | PA | 7-0 | 25-53-13 | D05216P | | | | 4 | | | D00820 | 4 | | | 150-199, 275-299 |
| 005 | 20 | | PA | 5-0 | 25-53-16 | D05216P | | | | 5 | | | D00820 | 5 | | | 050-099 |
| 005 | 20 | | PA | 7-0 | 25-53-16 | D05216P | | | | 5 | | | D00820 | 5 | | | 150-199, 275-299 |
| 006 | 20 | | PA | 5-0 | 25-53-16 | D05216P | | | | 6 | | | D00820 | 6 | | | 050-099 |
| 006 | 20 | | PA | 7-0 | 25-53-16 | D05216P | | | | 6 | | | D00820 | 6 | | | 150-199, 275-299 |
| 007 | 20 | | PA | 5-0 | 25-53-17 | D05216P | | | | 7 | | | D00820 | 7 | | | 050-099 |
| 007 | 20 | | PA | 7-0 | 25-53-17 | D05216P | | | | 7 | | | D00820 | 7 | | | 150-199, 275-299 |
| 008 | 20 | | PA | 5-0 | 25-53-17 | D05216P | | | | 8 | | | D00820 | 8 | | | 050-099 |
| 008 | 20 | | PA | 7-0 | 25-53-17 | D05216P | | | | 8 | | | D00820 | 8 | | | 150-199, 275-299 |
| 009 | 20 | | PA | 7-0 | 25-53-13 | D05216P | | | | 9 | | | D00820 | 9 | | | 150-199, 275-299 |
| 010 | 20 | | PA | 6-0 | 25-53-13 | D05216P | | | | 21 | | | D00820 | 9 | | | 050-099 |
| 011 | 20 | | PA | 6-0 | 25-53-11 | D05216P | | | | 11 | | | D00818 | 1 | | | 050-099 |
| 011 | 20 | | PA | 8-0 | 25-53-11 | D05216P | | | | 11 | | | D00818 | 1 | | | 150-199, 275-299 |
| 012 | 20 | | PA | 10-0 | 25-53-11 | GD04324 | | | S.. | 2 | | | D00818 | 2 | | | 050-099 |
| 012 | 20 | | PA | 9-0 | 25-53-11 | GD04324 | | | S.. | 2 | | | D00818 | 2 | | | 150-199, 275-299 |
| 013 | 20 | | PA | 6-0 | 25-53-13 | D05216P | | | | 13 | | | D00818 | 3 | | | 050-099 |
| 013 | 20 | | PA | 8-0 | 25-53-13 | D05216P | | | | 13 | | | D00818 | 3 | | | 150-199, 275-299 |
| 014 | 20 | | PA | 6-0 | 25-53-14 | D05216P | | | | 14 | | | D00818 | 4 | | | 050-099 |
| 014 | 20 | | PA | 8-0 | 25-53-14 | D05216P | | | | 14 | | | D00818 | 4 | | | 150-199, 275-299 |
| 015 | 20 | | PA | 6-0 | 25-53-14 | D05216P | | | | 15 | | | D00818 | 5 | | | 050-099 |
| 015 | 20 | | PA | 8-0 | 25-53-14 | D05216P | | | | 15 | | | D00818 | 5 | | | 150-199, 275-299 |
| 016 | 20 | | PA | 6-0 | 25-53-13 | D05216P | | | | 16 | | | D00818 | 6 | | | 050-099 |
| 016 | 20 | | PA | 8-0 | 25-53-13 | D05216P | | | | 16 | | | D00818 | 6 | | | 150-199, 275-299 |
| 017 | 20 | | PA | 6-0 | 25-53-13 | D05216P | | | | 17 | | | D00818 | 7 | | | 050-099 |
| 017 | 20 | | PA | 8-0 | 25-53-13 | D05216P | | | | 17 | | | D00818 | 7 | | | 150-199, 275-299 |
| 018 | 20 | | PA | 6-0 | 25-53-15 | D05216P | | | | 18 | | | D00818 | 8 | | | 050-099 |
| 018 | 20 | | PA | 8-0 | 25-53-14 | D05216P | | | | 18 | | | D00818 | 8 | | | 150-199, 275-299 |
| 022 | 20 | | PA | 6-0 | 25-53-16 | D05216P | | | | 22 | | | D00820 | 15 | | | 050-099 |
| 022 | 20 | | PA | 7-0 | 25-53-16 | D05216P | | | | 22 | | | D00820 | 15 | | | 150-199, 275-299 |
| 023 | 20 | | PA | 6-0 | 25-53-17 | D05216P | | | | 23 | | | D00820 | 13 | | | 050-099 |
| 023 | 20 | | PA | 7-0 | 25-53-17 | D05216P | | | | 23 | | | D00820 | 13 | | | 150-199, 275-299 |
| 024 | 20 | | PA | 6-0 | 25-53-17 | D05216P | | | | 24 | | | D00820 | 14 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0700 | 286T0700 | | | FWD CARGO LOADING CONTROL (P24) (continued) | | | | | | | | | | | |
| 024 | 20 | | PA | 7-0 | 25-53-17 | D05216P | | 24 | | | D00820 | | 14 | | 150-199, 275-299 |
| 033 | 20 | | PA | 9-0 | 25-53-11 | GD04324 | | D.. | 2 | | D00820 | | 3 | | ALL |
| 034 | 20 | | PA | 10-0 | 25-53-11 | GD04324 | | D.. | 2 | | SP00766 | | | 1A | 050-099 |
| 034 | 20 | | PA | 9-0 | 25-53-11 | GD04324 | | D.. | 2 | | SP00766 | | | 1A | 150-199, 275-299 |
| A-A | | | | 0-0 | 25-53-11 | L00595 | | | =1 | | SP00764 | | | 1A | ALL |
| A-B | | | | 0-0 | 25-53-11 | L00595 | | | =2 | | SP00766 | | | 1A | ALL |
| W0702 | 286T0702 | | | FWD CARGO GUIDE ACTUATORS AND DOOR STOPS | | | | | | | | | | | |
| 001 | 20 | | PA | 17-0 | 25-53-15 | D01962 | | | 1 | | GD04322 | | A.. | 2 | 050-099 |
| 001 | 20 | | PA | 16-0 | 25-53-15 | D01962 | | | 1 | | GD00202 | | A.. | 2 | 150-199, 275-299 |
| 002 | 20 | | PA | 20-0 | 25-53-15 | D01962 | | | 2 | | D05218P | | | 1 | 050-099 |
| 002 | 20 | | PA | 21-0 | 25-53-15 | D01962 | | | 2 | | D05218P | | | 1 | 150-199, 275-299 |
| 003 | 20 | | PA | 20-0 | 25-53-15 | D01962 | | | 4 | | D05218P | | | 2 | 050-099 |
| 003 | 20 | | PA | 18-0 | 25-53-15 | D01962 | | | 4 | | D05218P | | | 2 | 150-199, 275-299 |
| 004 | 20 | | PA | 17-0 | 25-53-15 | D01962 | | | 12 | | GD04322 | | S.. | 2 | 050-099 |
| 004 | 20 | | PA | 16-0 | 25-53-15 | D01962 | | | 12 | | GD00202 | | S.. | 2 | 150-199, 275-299 |
| 011 | 20 | | PA | 17-0 | 25-53-15 | D01964 | | | 1 | | GD04320 | | A.. | 2 | 050-099 |
| 011 | 20 | | PA | 18-0 | 25-53-15 | D01964 | | | 1 | | GD00202 | | A.. | 2 | 150-199, 275-299 |
| 012 | 20 | | PA | 21-0 | 25-53-15 | D01964 | | | 2 | | D05218P | | | 3 | 050-099 |
| 012 | 20 | | PA | 20-0 | 25-53-15 | D01964 | | | 2 | | D05218P | | | 3 | 150-199, 275-299 |
| 013 | 20 | | PA | 21-0 | 25-53-15 | D01964 | | | 4 | | D05218P | | | 4 | ALL |
| 014 | 20 | | PA | 17-0 | 25-53-15 | D01964 | | | 12 | | GD04320 | | S.. | 2 | 050-099 |
| 014 | 20 | | PA | 18-0 | 25-53-15 | D01964 | | | 12 | | GD00202 | | S.. | 2 | 150-199, 275-299 |
| 021 | 20 | | PA | 19-0 | 25-53-15 | D01966 | | | 1 | | GD04322 | | A.. | 2 | 050-099 |
| 021 | 20 | | PA | 19-0 | 25-53-15 | D01966 | | | 1 | | GD00202 | | A.. | 2 | 150-199, 275-299 |
| 022 | 20 | | PA | 25-0 | 25-53-15 | D01966 | | | 2 | | D05218P | | | 5 | 050-099 |
| 022 | 20 | | PA | 21-0 | 25-53-15 | D01966 | | | 2 | | D05218P | | | 5 | 150-199, 275-299 |
| 023 | 20 | | PA | 25-0 | 25-53-15 | D01966 | | | 4 | | D05218P | | | 6 | 050-099 |
| 023 | 20 | | PA | 23-0 | 25-53-15 | D01966 | | | 4 | | D05218P | | | 6 | 150-199, 275-299 |
| 024 | 20 | | PA | 19-0 | 25-53-15 | D01966 | | | 12 | | GD04322 | | S.. | 2 | 050-099 |
| 024 | 20 | | PA | 19-0 | 25-53-15 | D01966 | | | 12 | | GD00202 | | S.. | 2 | 150-199, 275-299 |
| 031 | 20 | | PA | 12-0 | 25-53-15 | D01968 | | | 1 | | GD00384 | | A.. | 2 | 050-099 |
| 031 | 20 | | PA | 21-0 | 25-53-15 | D01968 | | | 1 | | GD04170 | | A.. | 2 | 150-199, 275-299 |
| 032 | 20 | | PA | 25-0 | 25-53-15 | D01968 | | | 2 | | D05218P | | | 7 | 050-099 |
| 032 | 20 | | PA | 24-0 | 25-53-15 | D01968 | | | 2 | | D05218P | | | 7 | 150-199, 275-299 |
| 033 | 20 | | PA | 25-0 | 25-53-15 | D01968 | | | 4 | | D05218P | | | 8 | 050-099 |
| 033 | 20 | | PA | 24-0 | 25-53-15 | D01968 | | | 4 | | D05218P | | | 8 | 150-199, 275-299 |
| 034 | 20 | | PA | 12-0 | 25-53-15 | D01968 | | | 12 | | GD00384 | | S.. | 2 | 050-099 |
| 034 | 20 | | PA | 21-0 | 25-53-15 | D01968 | | | 12 | | GD04170 | | S.. | 2 | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 2

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0702 | 286T0702 | | | FWD CARGO GUIDE ACTUATORS AND DOOR STOPS (continued) | | | | | | | | | | | | | | |
| 041 | 20 | | PA | 10-0 | 25-53-15 | D01970 | | | | 1 | | | | GD00384 | A.. | 2 | | 050-099 |
| 041 | 20 | | PA | 19-0 | 25-53-15 | D01970 | | | | 1 | | | | GD04170 | A.. | 2 | | 150-199, 275-299 |
| 042 | 20 | | PA | 26-0 | 25-53-15 | D01970 | | | | 2 | | | | D05218P | | 9 | | 050-099 |
| 042 | 20 | | PA | 25-0 | 25-53-15 | D01970 | | | | 2 | | | | D05218P | | 9 | | 150-199, 275-299 |
| 043 | 20 | | PA | 26-0 | 25-53-15 | D01970 | | | | 4 | | | | D05218P | | 10 | | 050-099 |
| 043 | 20 | | PA | 25-0 | 25-53-15 | D01970 | | | | 4 | | | | D05218P | | 10 | | 150-199, 275-299 |
| 044 | 20 | | PA | 10-0 | 25-53-15 | D01970 | | | | 12 | | | | GD00384 | S.. | 2 | | 050-099 |
| 044 | 20 | | PA | 19-0 | 25-53-15 | D01970 | | | | 12 | | | | GD04170 | S.. | 2 | | 150-199, 275-299 |
| 051 | 20 | | PA | 13-0 | 25-53-15 | D01972 | | | | 1 | | | | GD00384 | A.. | 2 | | 050-099 |
| 051 | 20 | | PA | 21-0 | 25-53-15 | D01972 | | | | 1 | | | | GD04170 | A.. | 2 | | 150-199, 275-299 |
| 052 | 20 | | PA | 28-0 | 25-53-15 | D01972 | | | | 2 | | | | D05218P | | 11 | | ALL |
| 053 | 20 | | PA | 28-0 | 25-53-15 | D01972 | | | | 4 | | | | D05218P | | 12 | | ALL |
| 054 | 20 | | PA | 13-0 | 25-53-15 | D01972 | | | | 12 | | | | GD00384 | S.. | 2 | | 050-099 |
| 054 | 20 | | PA | 21-0 | 25-53-15 | D01972 | | | | 12 | | | | GD04170 | S.. | 2 | | 150-199, 275-299 |
| 061 | 20 | | PA | 18-0 | 25-53-16 | D01974 | | | | 1 | | | | GD04326 | A.. | 2 | | 050-099 |
| 061 | 20 | | PA | 21-0 | 25-53-16 | D01976 | | | | 1 | | | | GD00252 | A.. | 2 | | 150-199, 275-299 |
| 062 | 20 | | PA | 22-0 | 25-53-16 | D01974 | | | | 2 | | | | D05218P | | 13 | | 050-099 |
| 062 | 20 | | PA | 22-0 | 25-53-16 | D01976 | | | | 2 | | | | D05218P | | 13 | | 150-199, 275-299 |
| 063 | 20 | | PA | 22-0 | 25-53-16 | D01974 | | | | 5 | | | | D05218P | | 14 | | 050-099 |
| 063 | 20 | | PA | 22-0 | 25-53-16 | D01976 | | | | 5 | | | | D05218P | | 14 | | 150-199, 275-299 |
| 064 | 20 | | PA | 18-0 | 25-53-16 | D01974 | | | | 12 | | | | GD04326 | S.. | 2 | | 050-099 |
| 064 | 20 | | PA | 21-0 | 25-53-16 | D01976 | | | | 12 | | | | GD00252 | S.. | 2 | | 150-199, 275-299 |
| 071 | 20 | | PA | 23-0 | 25-53-16 | D01976 | | | | 1 | | | | GD00252 | A.. | 2 | | 050-099 |
| 071 | 20 | | PA | 13-0 | 25-53-16 | D01974 | | | | 1 | | | | GD00202 | A.. | 2 | | 150-199, 275-299 |
| 072 | 20 | | PA | 23-0 | 25-53-16 | D01976 | | | | 2 | | | | D05218P | | 15 | | 050-099 |
| 072 | 20 | | PA | 23-0 | 25-53-16 | D01974 | | | | 2 | | | | D05218P | | 15 | | 150-199, 275-299 |
| 073 | 20 | | PA | 23-0 | 25-53-16 | D01976 | | | | 5 | | | | D05218P | | 16 | | 050-099 |
| 073 | 20 | | PA | 23-0 | 25-53-16 | D01974 | | | | 5 | | | | D05218P | | 16 | | 150-199, 275-299 |
| 074 | 20 | | PA | 23-0 | 25-53-16 | D01976 | | | | 12 | | | | GD00252 | S.. | 2 | | 050-099 |
| 074 | 20 | | PA | 13-0 | 25-53-16 | D01974 | | | | 12 | | | | GD00202 | S.. | 2 | | 150-199, 275-299 |
| 081 | 20 | | PA | 19-0 | 25-53-16 | D01978 | | | | 1 | | | | GD04326 | A.. | 2 | | 050-099 |
| 081 | 20 | | PA | 23-0 | 25-53-16 | D01980 | | | | 1 | | | | GD00252 | A.. | 2 | | 150-199, 275-299 |
| 082 | 20 | | PA | 23-0 | 25-53-16 | D01978 | | | | 2 | | | | D05218P | | 17 | | 050-099 |
| 082 | 20 | | PA | 25-0 | 25-53-16 | D01980 | | | | 2 | | | | D05218P | | 17 | | 150-199, 275-299 |
| 083 | 20 | | PA | 23-0 | 25-53-16 | D01978 | | | | 5 | | | | D05218P | | 18 | | 050-099 |
| 083 | 20 | | PA | 25-0 | 25-53-16 | D01980 | | | | 5 | | | | D05218P | | 18 | | 150-199, 275-299 |
| 084 | 20 | | PA | 19-0 | 25-53-16 | D01978 | | | | 12 | | | | GD04326 | S.. | 2 | | 050-099 |
| 084 | 20 | | PA | 23-0 | 25-53-16 | D01980 | | | | 12 | | | | GD00252 | S.. | 2 | | 150-199, 275-299 |
| 091 | 20 | | PA | 21-0 | 25-53-16 | D01980 | | | | 1 | | | | GD04326 | A.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0702 | 286T0702 | | | FWD CARGO GUIDE ACTUATORS AND DOOR STOPS (continued) | | | | | | | | | | | |
| 091 | 20 | | PA | 15-0 | 25-53-16 | D01978 | | | 1 | | GD00202 | A.. | 2 | | 150-199, 275-299 |
| 092 | 20 | | PA | 24-0 | 25-53-16 | D01980 | | | 2 | | D05218P | | 19 | | 050-099 |
| 092 | 20 | | PA | 25-0 | 25-53-16 | D01978 | | | 2 | | D05218P | | 19 | | 150-199, 275-299 |
| 093 | 20 | | PA | 24-0 | 25-53-16 | D01980 | | | 5 | | D05218P | | 20 | | 050-099 |
| 093 | 20 | | PA | 25-0 | 25-53-16 | D01978 | | | 5 | | D05218P | | 20 | | 150-199, 275-299 |
| 094 | 20 | | PA | 21-0 | 25-53-16 | D01980 | | | 12 | | GD04326 | S.. | 2 | | 050-099 |
| 094 | 20 | | PA | 15-0 | 25-53-16 | D01978 | | | 12 | | GD00202 | S.. | 2 | | 150-199, 275-299 |
| 101 | 20 | | PA | 21-0 | 25-53-17 | D02314 | | | 1 | | GD04326 | A.. | 2 | | 050-099 |
| 101 | 20 | | PA | 20-0 | 25-53-17 | D02314 | | | 1 | | GD04326 | A.. | 2 | | 150-199, 275-299 |
| 102 | 20 | | PA | 25-0 | 25-53-17 | D02314 | | | 2 | | D05218P | | 21 | | 050-099 |
| 102 | 20 | | PA | 24-0 | 25-53-17 | D02314 | | | 2 | | D05218P | | 21 | | 150-199, 275-299 |
| 103 | 20 | | PA | 25-0 | 25-53-17 | D02314 | | | 3 | | D05218P | | 22 | | 050-099 |
| 103 | 20 | | PA | 24-0 | 25-53-17 | D02314 | | | 3 | | D05218P | | 22 | | 150-199, 275-299 |
| 104 | 20 | | PA | 21-0 | 25-53-17 | D02314 | | | 12 | | GD04326 | S.. | 2 | | 050-099 |
| 104 | 20 | | PA | 20-0 | 25-53-17 | D02314 | | | 12 | | GD04326 | S.. | 2 | | 150-199, 275-299 |
| 105 | 20 | | PA | 25-0 | 25-53-17 | D02314 | | | 14 | | D05218P | | 23 | | 050-099 |
| 105 | 20 | | PA | 24-0 | 25-53-17 | D02314 | | | 14 | | D05218P | | 23 | | 150-199, 275-299 |
| 111 | 20 | | PA | 23-0 | 25-53-17 | D02316 | | | 1 | | GD04326 | A.. | 2 | | 050-099 |
| 111 | 20 | | PA | 22-0 | 25-53-17 | D02316 | | | 1 | | GD04326 | A.. | 2 | | 150-199, 275-299 |
| 112 | 20 | | PA | 26-0 | 25-53-17 | D02316 | | | 2 | | D05218P | | 24 | | ALL |
| 113 | 20 | | PA | 26-0 | 25-53-17 | D02316 | | | 3 | | D05218P | | 25 | | ALL |
| 114 | 20 | | PA | 23-0 | 25-53-17 | D02316 | | | 12 | | GD04326 | S.. | 2 | | 050-099 |
| 114 | 20 | | PA | 22-0 | 25-53-17 | D02316 | | | 12 | | GD04326 | S.. | 2 | | 150-199, 275-299 |
| 115 | 20 | | PA | 26-0 | 25-53-17 | D02316 | | | 14 | | D05218P | | 26 | | ALL |
| 121 | 20 | | PA | 12-0 | 25-53-17 | D00638 | | | 1 | | GD00398 | A.. | 2 | | 050-099 |
| 121 | 20 | | PA | 11-0 | 25-53-17 | D00638 | | | 1 | | GD00398 | A.. | 2 | | 150-199, 275-299 |
| 122 | 20 | | PA | 48-0 | 25-53-17 | D00638 | | | 2 | | D05218P | | 27 | | 050-099 |
| 122 | 20 | | PA | 46-0 | 25-53-17 | D00638 | | | 2 | | D05218P | | 27 | | 150-199, 275-299 |
| 123 | 20 | | PA | 48-0 | 25-53-17 | D00638 | | | 3 | | D05218P | | 28 | | 050-099 |
| 123 | 20 | | PA | 46-0 | 25-53-17 | D00638 | | | 3 | | D05218P | | 28 | | 150-199, 275-299 |
| 124 | 20 | | PA | 12-0 | 25-53-17 | D00638 | | | 12 | | GD00398 | S.. | 2 | | 050-099 |
| 124 | 20 | | PA | 11-0 | 25-53-17 | D00638 | | | 12 | | GD00398 | S.. | 2 | | 150-199, 275-299 |
| 125 | 20 | | PA | 48-0 | 25-53-17 | D00638 | | | 14 | | D05218P | | 29 | | 050-099 |
| 125 | 20 | | PA | 46-0 | 25-53-17 | D00638 | | | 14 | | D05218P | | 29 | | 150-199, 275-299 |
| 131 | 20 | | PA | 10-0 | 25-53-17 | D00690 | | | 1 | | GD04170 | A.. | 2 | | 050-099 |
| 131 | 20 | | PA | 9-0 | 25-53-17 | D00690 | | | 1 | | GD04170 | A.. | 2 | | 150-199, 275-299 |
| 132 | 20 | | PA | 49-0 | 25-53-17 | D00690 | | | 2 | | D05218P | | 30 | | 050-099 |
| 132 | 20 | | PA | 46-0 | 25-53-17 | D00690 | | | 2 | | D05218P | | 30 | | 150-199, 275-299 |
| 133 | 20 | | PA | 49-0 | 25-53-17 | D00690 | | | 3 | | D05218P | | 31 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 4

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0702 | 286T0702 | | | FWD CARGO GUIDE ACTUATORS AND DOOR STOPS (continued) | | | | | | | | | | | | |
| 133 | 20 | | PA | 46-0 | 25-53-17 | D00690 | | | | | | | 31 | | | 150-199, 275-299 |
| 134 | 20 | | PA | 10-0 | 25-53-17 | D00690 | | | | | | | S.. | 2 | | 050-099 |
| 134 | 20 | | PA | 9-0 | 25-53-17 | D00690 | | | | | | | S.. | 2 | | 150-199, 275-299 |
| 135 | 20 | | PA | 49-0 | 25-53-17 | D00690 | | | | | | | 32 | | | 050-099 |
| 135 | 20 | | PA | 46-0 | 25-53-17 | D00690 | | | | | | | 32 | | | 150-199, 275-299 |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) | | | | | | | | | | | | |
| 001 | 20 | | PA | 57-0 | 25-53-14 | D01252 | | | | | | | 37 | | | 050-099 |
| 001 | 20 | | PA | 6-0 | 25-53-14 | D01252 | | | | | | | | 9 | | 150-199, 275-299 |
| 002 | 20 | | PA | 57-0 | 25-53-14 | D01252 | | | | | | | 38 | | | 050-099 |
| 002 | 20 | | PA | 36-0 | 25-53-14 | D05224P | | | | | | | | 9 | | 150-199, 275-299 |
| 003 | 20 | | PA | 21-0 | 25-53-14 | D01252 | | | | | | | D.. | 2 | | 050-099 |
| 003 | 20 | | PA | 11-0 | 25-53-14 | D01252 | | | | | | | D.. | 2 | | 150-199, 275-299 |
| 005 | 18 | | PA | 21-0 | 25-53-12 | D01252 | | | | | | | A.. | 2 | | 050-099 |
| 005 | 18 | | PA | 11-0 | 25-53-12 | D01252 | | | | | | | A.. | 2 | | 150-199, 275-299 |
| 006 | 20 | | PA | 21-0 | 25-53-14 | D01252 | | | | | | | A.. | 2 | | 050-099 |
| 006 | 20 | | PA | 36-0 | 25-53-14 | D05224P | | | | | | | | 9 | | 150-199, 275-299 |
| 008 | 20 | | PA | 21-0 | 25-53-12 | D01252 | | | | | | | S.. | 2 | | 050-099 |
| 008 | 20 | | PA | 11-0 | 25-53-12 | D01252 | | | | | | | S.. | 2 | | 150-199, 275-299 |
| 009 | 20 | | PA | 21-0 | 25-53-12 | D01252 | | | | | | | S.. | 2 | | 050-099 |
| 009 | 20 | | PA | 11-0 | 25-53-12 | D01252 | | | | | | | S.. | 2 | | 150-199, 275-299 |
| 011 | 20 | | PA | 24-0 | 25-53-14 | D01214 | | | | | | | | 4 | | 050-099 |
| 011 | 20 | | PA | 23-0 | 25-53-14 | D01214 | | | | | | | | 4 | | 150-199, 275-299 |
| 012 | 20 | | PA | 24-0 | 25-53-14 | D01214 | | | | | | | | 5 | | 050-099 |
| 012 | 20 | | PA | 27-0 | 25-53-14 | D01214 | | | | | | | | 5 | | 150-199, 275-299 |
| 013 | 20 | | PA | 16-0 | 25-53-14 | D01212 | | | | | | | A.. | 2 | | 050-099 |
| 013 | 20 | | PA | 19-0 | 25-53-14 | D01212 | | | | | | | D.. | 2 | | 150-199, 275-299 |
| 015 | 18 | | PA | 16-0 | 25-53-12 | D01212 | | | | | | | A.. | 2 | | 050-099 |
| 015 | 18 | | PA | 19-0 | 25-53-12 | D01212 | | | | | | | A.. | 2 | | 150-199, 275-299 |
| 016 | 20 | | PA | 16-0 | 25-53-14 | D01212 | | | | | | | D.. | 2 | | 050-099 |
| 016 | 20 | | PA | 19-0 | 25-53-14 | D01212 | | | | | | | A.. | 2 | | 150-199, 275-299 |
| 018 | 20 | | PA | 16-0 | 25-53-12 | D01212 | | | | | | | S.. | 2 | | 050-099 |
| 018 | 20 | | PA | 19-0 | 25-53-12 | D01212 | | | | | | | S.. | 2 | | 150-199, 275-299 |
| 019 | 20 | | PA | 16-0 | 25-53-12 | D01212 | | | | | | | S.. | 2 | | 050-099 |
| 019 | 20 | | PA | 19-0 | 25-53-12 | D01212 | | | | | | | S.. | 2 | | 150-199, 275-299 |
| 021 | 20 | | PA | 10-0 | 25-53-14 | D01216 | | | | | | | | 9 | | 050-099 |
| 021 | 20 | | PA | 74-0 | 25-53-14 | D01216 | | | | | | | | 33 | | 150-199, 275-299 |
| 022 | 20 | | PA | 10-0 | 25-53-14 | D01216 | | | | | | | | 9 | | 050-099 |
| 022 | 20 | | PA | 74-0 | 25-53-14 | D01216 | | | | | | | | 29 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | | |
| 023 | 20 | | PA | 12-0 | 25-53-14 | D01216 | | | 3 | | | | GD00322 | D.. | 2 | | 050-099 |
| 023 | 20 | | PA | 12-0 | 25-53-14 | D01216 | | | 3 | | | | GD00280 | D.. | 2 | | 150-199, 275-299 |
| 025 | 18 | | PA | 12-0 | 25-53-12 | D01216 | | | 5 | DK | | | GD00322 | A.. | 2 | | 050-099 |
| 025 | 18 | | PA | 12-0 | 25-53-12 | D11598 | | | 5 | DK | | | GD00322 | A.. | 2 | | 150-199, 275-299 |
| 026 | 20 | | PA | 12-0 | 25-53-14 | D01216 | | | 6 | | | | GD00322 | A.. | 2 | | 050-099 |
| 026 | 20 | | PA | 12-0 | 25-53-14 | D01216 | | | 6 | | | | GD00280 | A.. | 2 | | 150-199, 275-299 |
| 028 | 20 | | PA | 12-0 | 25-53-12 | D01216 | | | 8 | | | | GD00322 | S.. | 2 | | 050-099 |
| 028 | 20 | | PA | 12-0 | 25-53-12 | D11598 | | | 8 | | | | GD00322 | S.. | 2 | | 150-199, 275-299 |
| 029 | 20 | | PA | 12-0 | 25-53-12 | D01216 | | | 9 | | | | GD00322 | S.. | 2 | | 050-099 |
| 029 | 20 | | PA | 12-0 | 25-53-12 | D11598 | | | 9 | | | | GD00322 | S.. | 2 | | 150-199, 275-299 |
| 031 | 20 | | PA | 7-0 | 25-53-14 | D01220 | | | 1 | | | | SM00031 | | 9 | | 050-099 |
| 031 | 20 | | PA | 11-0 | 25-53-14 | D01220 | | | 1 | | | | SM00043 | | 9 | | 150-199, 275-299 |
| 032 | 20 | | PA | 7-0 | 25-53-14 | D01220 | | | 2 | | | | SM00032 | | 9 | | 050-099 |
| 032 | 20 | | PA | 11-0 | 25-53-14 | D01220 | | | 2 | | | | SM00045 | | 9 | | 150-199, 275-299 |
| 033 | 20 | | PA | 22-0 | 25-53-14 | D01220 | | | 3 | | | | GD04322 | D.. | 2 | | 050-099 |
| 033 | 20 | | PA | 15-0 | 25-53-14 | D01220 | | | 3 | | | | GD00322 | D.. | 2 | | 150-199, 275-299 |
| 035 | 18 | | PA | 22-0 | 25-53-12 | D01220 | | | 5 | DK | | | GD04322 | A.. | 2 | | 050-099 |
| 036 | 20 | | PA | 7-0 | 25-53-14 | D01220 | | | 6 | | | | SM00036 | | 9 | | 050-099 |
| 036 | 20 | | PA | 15-0 | 25-53-14 | D01220 | | | 6 | | | | GD00322 | A.. | 2 | | 150-199, 275-299 |
| 038 | 20 | | PA | 22-0 | 25-53-12 | D01220 | | | 8 | | | | GD04322 | S.. | 2 | | 050-099 |
| 039 | 20 | | PA | 22-0 | 25-53-12 | D01220 | | | 9 | | | | GD04322 | S.. | 2 | | 050-099 |
| 041 | 20 | | PA | 10-0 | 25-53-14 | D01230 | | | 1 | | | | SM00031 | | 9 | | 050-099 |
| 041 | 20 | | PA | 22-0 | 25-53-14 | D01224 | | | 1 | | | | SM00061 | | 9 | | 150-199, 275-299 |
| 042 | 20 | | PA | 10-0 | 25-53-14 | D01230 | | | 2 | | | | SM00032 | | 9 | | 050-099 |
| 042 | 20 | | PA | 22-0 | 25-53-14 | D01224 | | | 2 | | | | SM00062 | | 9 | | 150-199, 275-299 |
| 043 | 20 | | PA | 24-0 | 25-53-14 | D01230 | | | 3 | | | | GD04322 | D.. | 2 | | 050-099 |
| 043 | 20 | | PA | 10-0 | 25-53-14 | D01224 | | | 3 | | | | GD00214 | D.. | 2 | | 150-199, 275-299 |
| 045 | 18 | | PA | 21-0 | 25-53-12 | D01224 | | | 5 | DK | | | GD04326 | A.. | 2 | | 050-099 |
| 045 | 18 | | PA | 7-0 | 25-53-12 | D01232 | | | 5 | DK | | | GD00214 | A.. | 2 | | 150-199, 275-299 |
| 046 | 20 | | PA | 10-0 | 25-53-14 | D01230 | | | 6 | | | | SM00036 | | 9 | | 050-099 |
| 046 | 20 | | PA | 22-0 | 25-53-14 | D01224 | | | 6 | | | | SM00066 | | 9 | | 150-199, 275-299 |
| 048 | 20 | | PA | 21-0 | 25-53-12 | D01224 | | | 8 | | | | GD04326 | S.. | 2 | | 050-099 |
| 048 | 20 | | PA | 7-0 | 25-53-12 | D01232 | | | 8 | | | | GD00214 | S.. | 2 | | 150-199, 275-299 |
| 049 | 20 | | PA | 21-0 | 25-53-12 | D01224 | | | 9 | | | | GD04326 | S.. | 2 | | 050-099 |
| 049 | 20 | | PA | 7-0 | 25-53-12 | D01232 | | | 9 | | | | GD00214 | S.. | 2 | | 150-199, 275-299 |
| 051 | 20 | | PA | 6-0 | 25-53-14 | D01238 | | | 2 | | | | SM00051 | | 9 | | 050-099 |
| 051 | 20 | | PA | 5-0 | 25-53-14 | D01228 | | | 1 | | | | SM00031 | | 9 | | 150-199, 275-299 |
| 052 | 20 | | PA | 6-0 | 25-53-14 | D01238 | | | 1 | | | | SM00052 | | 9 | | 050-099 |
| 052 | 20 | | PA | 5-0 | 25-53-14 | D01228 | | | 2 | | | | SM00032 | | 9 | | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0700
Page 6
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | | |
| 053 | 20 | | PA | 6-0 | 25-53-14 | D01238 | | 3 | | | | | GD00202 | D.. | 2 | | 050-099 |
| 053 | 20 | | PA | 18-0 | 25-53-14 | D01228 | | 3 | | | | | GD04320 | D.. | 2 | | 150-199, 275-299 |
| 055 | 18 | | PA | 10-0 | 25-53-12 | D01228 | | 5 | DK | | | | GD00214 | A.. | 2 | | 050-099 |
| 055 | 18 | | PA | 20-0 | 25-53-12 | D11096 | | 5 | DK | | | | GD04326 | A.. | 2 | | 150-199, 275-299 |
| 056 | 20 | | PA | 6-0 | 25-53-14 | D01238 | | 6 | | | | | SM00056 | | 9 | | 050-099 |
| 056 | 20 | | PA | 6-0 | 25-53-14 | D01228 | | 6 | | | | | SM00053 | | 9 | | 150-199, 275-299 |
| 058 | 20 | | PA | 10-0 | 25-53-12 | D01228 | | 8 | | | | | GD00214 | S.. | 2 | | 050-099 |
| 058 | 20 | | PA | 29-0 | 25-53-12 | D11096 | | 8 | | | | | GD04326 | S.. | 2 | | 150-199, 275-299 |
| 059 | 20 | | PA | 10-0 | 25-53-12 | D01228 | | 9 | | | | | GD00214 | S.. | 2 | | 050-099 |
| 059 | 20 | | PA | 20-0 | 25-53-12 | D11096 | | 9 | | | | | GD04326 | S.. | 2 | | 150-199, 275-299 |
| 061 | 20 | | PA | 20-0 | 25-53-14 | D01232 | | 1 | | | | | SM00061 | | 9 | | ALL |
| 062 | 20 | | PA | 20-0 | 25-53-14 | D01232 | | 2 | | | | | SM00062 | | 9 | | ALL |
| 063 | 20 | | PA | 7-0 | 25-53-14 | D01232 | | 3 | | | | | GD00214 | D.. | 2 | | 050-099 |
| 063 | 20 | | PA | 8-0 | 25-53-14 | D01232 | | 3 | | | | | GD00214 | D.. | 2 | | 150-199, 275-299 |
| 065 | 18 | | PA | 7-0 | 25-53-12 | D01232 | | 5 | DK | | | | GD00214 | A.. | 2 | | 050-099 |
| 065 | 18 | | PA | 18-0 | 25-53-12 | D01228 | | 5 | DK | | | | GD04320 | A.. | 2 | | 150-199, 275-299 |
| 066 | 20 | | PA | 43-0 | 25-53-14 | D01232 | | 6 | | | | | D05224P | | 30 | | 050-099 |
| 066 | 20 | | PA | 44-0 | 25-53-14 | D01232 | | 6 | | | | | D05224P | | 44 | | 150-199, 275-299 |
| 068 | 20 | | PA | 7-0 | 25-53-12 | D01232 | | 8 | | | | | GD00214 | S.. | 2 | | 050-099 |
| 068 | 20 | | PA | 18-0 | 25-53-12 | D01228 | | 8 | | | | | GD04320 | S.. | 2 | | 150-199, 275-299 |
| 069 | 20 | | PA | 7-0 | 25-53-12 | D01232 | | 9 | | | | | GD00214 | S.. | 2 | | 050-099 |
| 069 | 20 | | PA | 18-0 | 25-53-12 | D01228 | | 9 | | | | | GD04320 | S.. | 2 | | 150-199, 275-299 |
| 071 | 20 | | PA | 24-0 | 25-53-14 | D01280 | | 1 | | | | | SM00052 | | 9 | | 050-099 |
| 071 | 20 | | PA | 20-0 | 25-53-14 | D01238 | | 2 | | | | | SM00052 | | 9 | | 150-199, 275-299 |
| 072 | 20 | | PA | 24-0 | 25-53-14 | D01280 | | 2 | | | | | SM00051 | | 9 | | 050-099 |
| 072 | 20 | | PA | 20-0 | 25-53-14 | D01238 | | 1 | | | | | SM00051 | | 9 | | 150-199, 275-299 |
| 073 | 20 | | PA | 8-0 | 25-53-14 | D01280 | | 3 | | | | | GD00252 | D.. | 2 | | 050-099 |
| 073 | 20 | | PA | 5-0 | 25-53-14 | D01238 | | 3 | | | | | GD00252 | D.. | 2 | | 150-199, 275-299 |
| 075 | 18 | | PA | 6-0 | 25-53-12 | D01238 | | 5 | DK | | | | GD00202 | A.. | 2 | | 050-099 |
| 075 | 18 | | PA | 14-0 | 25-53-12 | D01220 | | 5 | DK | | | | GD00322 | A.. | 2 | | 150-199, 275-299 |
| 076 | 20 | | PA | 24-0 | 25-53-14 | D01280 | | 6 | | | | | SM00056 | | 9 | | 050-099 |
| 076 | 20 | | PA | 20-0 | 25-53-14 | D01238 | | 6 | | | | | SM00056 | | 9 | | 150-199, 275-299 |
| 078 | 20 | | PA | 6-0 | 25-53-12 | D01238 | | 8 | | | | | GD00202 | S.. | 2 | | 050-099 |
| 078 | 20 | | PA | 14-0 | 25-53-12 | D01220 | | 8 | | | | | GD00322 | S.. | 2 | | 150-199, 275-299 |
| 079 | 20 | | PA | 6-0 | 25-53-12 | D01238 | | 9 | | | | | GD00202 | S.. | 2 | | 050-099 |
| 079 | 20 | | PA | 14-0 | 25-53-12 | D01220 | | 9 | | | | | GD00322 | S.. | 2 | | 150-199, 275-299 |
| 081 | 20 | | PA | 48-0 | 25-53-14 | D01242 | | 1 | | | | | D05224P | | 27 | | 050-099 |
| 081 | 20 | | PA | 73-0 | 25-53-14 | D01242 | | 1 | | | | | D05224P | | 9 | | 150-199, 275-299 |
| 082 | 20 | | PA | 48-0 | 25-53-14 | D01242 | | 2 | | | | | D05224P | | 28 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | | |
| 082 | 20 | | PA | 73-0 | 25-53-14 | D01242 | | | | | | | | | | | 150-199, 275-299 |
| 083 | 20 | | PA | 18-0 | 25-53-14 | D01242 | | | | | | | | | | | 050-099 |
| 083 | 20 | | PA | 13-0 | 25-53-14 | D01242 | | | | | | | | | | | 150-199, 275-299 |
| 085 | 18 | | PA | 18-0 | 25-53-12 | D01242 | | | | | | | | | | | 050-099 |
| 085 | 18 | | PA | 14-0 | 25-53-12 | D11640 | | | | | | | | | | | 150-199, 275-299 |
| 086 | 20 | | PA | 18-0 | 25-53-14 | D01242 | | | | | | | | | | | 050-099 |
| 086 | 20 | | PA | 13-0 | 25-53-14 | D01242 | | | | | | | | | | | 150-199, 275-299 |
| 088 | 20 | | PA | 18-0 | 25-53-12 | D01242 | | | | | | | | | | | 050-099 |
| 088 | 20 | | PA | 14-0 | 25-53-12 | D11640 | | | | | | | | | | | 150-199, 275-299 |
| 089 | 20 | | PA | 18-0 | 25-53-12 | D01242 | | | | | | | | | | | 050-099 |
| 089 | 20 | | PA | 14-0 | 25-53-12 | D11640 | | | | | | | | | | | 150-199, 275-299 |
| 091 | 20 | | PA | 4-0 | 25-53-14 | D01246 | | | | | | | | | | | 150-199, 275-299 |
| 092 | 20 | | PA | 23-0 | 25-53-14 | D01246 | | | | | | | | | | | 150-199, 275-299 |
| 093 | 20 | | PA | 18-0 | 25-53-14 | D01246 | | | | | | | | | | | 150-199, 275-299 |
| 095 | 18 | | PA | 18-0 | 25-53-12 | D01246 | | | | | | | | | | | ALL |
| 096 | 20 | | PA | 23-0 | 25-53-14 | D01246 | | | | | | | | | | | 150-199, 275-299 |
| 098 | 20 | | PA | 18-0 | 25-53-12 | D01246 | | | | | | | | | | | ALL |
| 099 | 20 | | PA | 18-0 | 25-53-12 | D01246 | | | | | | | | | | | ALL |
| 101 | 20 | | PA | 52-0 | 25-53-14 | D01250 | | | | | | | | | | | 050-099 |
| 101 | 20 | | PA | 5-0 | 25-53-14 | D01250 | | | | | | | | | | | 150-199, 275-299 |
| 102 | 20 | | PA | 52-0 | 25-53-14 | D01250 | | | | | | | | | | | 050-099 |
| 102 | 20 | | PA | 5-0 | 25-53-14 | D01250 | | | | | | | | | | | 150-199, 275-299 |
| 103 | 20 | | PA | 16-0 | 25-53-14 | D01250 | | | | | | | | | | | 050-099 |
| 103 | 20 | | PA | 6-0 | 25-53-14 | D01250 | | | | | | | | | | | 150-199, 275-299 |
| 105 | 18 | | PA | 16-0 | 25-53-12 | D01250 | | | | | | | | | | | 050-099 |
| 105 | 18 | | PA | 6-0 | 25-53-12 | D01250 | | | | | | | | | | | 150-199, 275-299 |
| 106 | 20 | | PA | 16-0 | 25-53-14 | D01250 | | | | | | | | | | | 050-099 |
| 106 | 20 | | PA | 5-0 | 25-53-14 | D01250 | | | | | | | | | | | 150-199, 275-299 |
| 108 | 20 | | PA | 16-0 | 25-53-12 | D01250 | | | | | | | | | | | 050-099 |
| 108 | 20 | | PA | 6-0 | 25-53-12 | D01250 | | | | | | | | | | | 150-199, 275-299 |
| 109 | 20 | | PA | 16-0 | 25-53-12 | D01250 | | | | | | | | | | | 050-099 |
| 109 | 20 | | PA | 6-0 | 25-53-12 | D01250 | | | | | | | | | | | 150-199, 275-299 |
| 111 | 20 | | PA | 18-0 | 25-53-14 | D01212 | | | | | | | | | | | 050-099 |
| 111 | 20 | | PA | 22-0 | 25-53-14 | D01212 | | | | | | | | | | | 150-199, 275-299 |
| 112 | 20 | | PA | 18-0 | 25-53-14 | D01212 | | | | | | | | | | | 050-099 |
| 112 | 20 | | PA | 22-0 | 25-53-14 | D01212 | | | | | | | | | | | 150-199, 275-299 |
| 113 | 20 | | PA | 22-0 | 25-53-14 | D01214 | | | | | | | | | | | 050-099 |
| 113 | 20 | | PA | 20-0 | 25-53-14 | D01214 | | | | | | | | | | | 150-199, 275-299 |
| 115 | 18 | | PA | 22-0 | 25-53-12 | D01214 | | | | | | | | | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 8

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | |
| 115 | 18 | PA | | 20-0 | 25-53-12 | D01214 | | 5 | DK | | | | GD04392 | A.. | 2 | 150-199, 275-299 |
| 116 | 20 | PA | | 22-0 | 25-53-14 | D01214 | | 6 | | | | | GD04392 | A.. | 2 | 050-099 |
| 116 | 20 | PA | | 20-0 | 25-53-14 | D01214 | | 6 | | | | | GD04392 | A.. | 2 | 150-199, 275-299 |
| 118 | 20 | PA | | 22-0 | 25-53-12 | D01214 | | 8 | | | | | GD04392 | S.. | 2 | 050-099 |
| 118 | 20 | PA | | 20-0 | 25-53-12 | D01214 | | 8 | | | | | GD04392 | S.. | 2 | 150-199, 275-299 |
| 119 | 20 | PA | | 22-0 | 25-53-12 | D01214 | | 9 | | | | | GD04392 | S.. | 2 | 050-099 |
| 119 | 20 | PA | | 20-0 | 25-53-12 | D01214 | | 9 | | | | | GD04392 | S.. | 2 | 150-199, 275-299 |
| 121 | 20 | PA | | 4-0 | 25-53-14 | D01218 | | 1 | | | | | SM00001 | | 9 | 050-099 |
| 121 | 20 | PA | | 8-0 | 25-53-14 | D01218 | | 1 | | | | | SM00048 | | 9 | 150-199, 275-299 |
| 122 | 20 | PA | | 4-0 | 25-53-14 | D01218 | | 2 | | | | | SM00002 | | 9 | 050-099 |
| 122 | 20 | PA | | 3-0 | 25-53-14 | D01218 | | 2 | | | | | SM00039 | | 9 | 150-199, 275-299 |
| 123 | 20 | PA | | 11-0 | 25-53-14 | D01218 | | 3 | | | | | GD04392 | D.. | 2 | 050-099 |
| 123 | 20 | PA | | 7-0 | 25-53-14 | D01218 | | 3 | | | | | GD04392 | D.. | 2 | 150-199, 275-299 |
| 125 | 18 | PA | | 11-0 | 25-53-12 | D01218 | | 5 | DK | | | | GD04392 | A.. | 2 | 050-099 |
| 125 | 18 | PA | | 7-0 | 25-53-12 | D01218 | | 5 | DK | | | | GD04392 | A.. | 2 | 150-199, 275-299 |
| 126 | 20 | PA | | 11-0 | 25-53-14 | D01218 | | 6 | | | | | GD04392 | A.. | 2 | 050-099 |
| 126 | 20 | PA | | 7-0 | 25-53-14 | D01218 | | 6 | | | | | GD04392 | A.. | 2 | 150-199, 275-299 |
| 128 | 20 | PA | | 11-0 | 25-53-12 | D01218 | | 8 | | | | | GD04392 | S.. | 2 | 050-099 |
| 128 | 20 | PA | | 7-0 | 25-53-12 | D01218 | | 8 | | | | | GD04392 | S.. | 2 | 150-199, 275-299 |
| 129 | 20 | PA | | 11-0 | 25-53-12 | D01218 | | 9 | | | | | GD04392 | S.. | 2 | 050-099 |
| 129 | 20 | PA | | 7-0 | 25-53-12 | D01218 | | 9 | | | | | GD04392 | S.. | 2 | 150-199, 275-299 |
| 131 | 20 | PA | | 10-0 | 25-53-14 | D01248 | | 1 | | | | | SM00041 | | 9 | 050-099 |
| 131 | 20 | PA | | 8-0 | 25-53-14 | D01222 | | 1 | | | | | SM00048 | | 9 | 150-199, 275-299 |
| 132 | 20 | PA | | 10-0 | 25-53-14 | D01248 | | 2 | | | | | SM00042 | | 9 | 050-099 |
| 132 | 20 | PA | | 14-0 | 25-53-14 | D01222 | | 2 | | | | | SM00039 | | 9 | 150-199, 275-299 |
| 133 | 20 | PA | | 22-0 | 25-53-14 | D01248 | | 3 | | | | | GD04320 | D.. | 2 | 050-099 |
| 133 | 20 | PA | | 18-0 | 25-53-14 | D01222 | | 3 | | | | | GD00322 | D.. | 2 | 150-199, 275-299 |
| 135 | 18 | PA | | 17-0 | 25-53-12 | D01222 | | 5 | DK | | | | GD00322 | A.. | 2 | 050-099 |
| 135 | 18 | PA | | 18-0 | 25-53-12 | D01222 | | 5 | DK | | | | GD00322 | A.. | 2 | 150-199, 275-299 |
| 136 | 20 | PA | | 10-0 | 25-53-14 | D01248 | | 6 | | | | | SM00046 | | 9 | 050-099 |
| 136 | 20 | PA | | 18-0 | 25-53-14 | D01222 | | 6 | | | | | GD00322 | A.. | 2 | 150-199, 275-299 |
| 138 | 20 | PA | | 17-0 | 25-53-12 | D01222 | | 8 | | | | | GD00322 | S.. | 2 | 050-099 |
| 138 | 20 | PA | | 18-0 | 25-53-12 | D01222 | | 8 | | | | | GD00322 | S.. | 2 | 150-199, 275-299 |
| 139 | 20 | PA | | 17-0 | 25-53-12 | D01222 | | 9 | | | | | GD00322 | S.. | 2 | 050-099 |
| 139 | 20 | PA | | 18-0 | 25-53-12 | D01222 | | 9 | | | | | GD00322 | S.. | 2 | 150-199, 275-299 |
| 141 | 20 | PA | | 11-0 | 25-53-14 | D01244 | | 2 | | | | | SM00041 | | 9 | 050-099 |
| 141 | 20 | PA | | 6-0 | 25-53-14 | D01226 | | 1 | | | | | SM00063 | | 9 | 150-199, 275-299 |
| 142 | 20 | PA | | 11-0 | 25-53-14 | D01244 | | 1 | | | | | SM00042 | | 9 | 050-099 |
| 142 | 20 | PA | | 16-0 | 25-53-14 | D01226 | | 2 | | | | | SM00058 | | 9 | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | | |
| 143 | 20 | | PA | 23-0 | 25-53-14 | D01244 | | 3 | | | | | GD04322 | D.. | 2 | | 050-099 |
| 143 | 20 | | PA | 20-0 | 25-53-14 | D01226 | | 3 | | | | | GD04322 | D.. | 2 | | 150-199, 275-299 |
| 145 | 18 | | PA | 23-0 | 25-53-12 | D01226 | | 5 | DK | | | | GD04394 | A.. | 2 | | 050-099 |
| 145 | 18 | | PA | 9-0 | 25-53-12 | D01236 | | 5 | DK | | | | GD04780 | A.. | 2 | | 150-199, 275-299 |
| 146 | 20 | | PA | 11-0 | 25-53-14 | D01244 | | 6 | | | | | SM00046 | | 9 | | 050-099 |
| 146 | 20 | | PA | 16-0 | 25-53-14 | D01226 | | 6 | | | | | SM00065 | | 9 | | 150-199, 275-299 |
| 148 | 20 | | PA | 23-0 | 25-53-12 | D01226 | | 8 | | | | | GD04394 | S.. | 2 | | 050-099 |
| 148 | 20 | | PA | 9-0 | 25-53-12 | D01236 | | 8 | | | | | GD04780 | S.. | 2 | | 150-199, 275-299 |
| 149 | 20 | | PA | 23-0 | 25-53-12 | D01226 | | 9 | | | | | GD04394 | S.. | 2 | | 050-099 |
| 149 | 20 | | PA | 9-0 | 25-53-12 | D01236 | | 9 | | | | | GD04780 | S.. | 2 | | 150-199, 275-299 |
| 151 | 20 | | PA | 6-0 | 25-53-14 | D01240 | | 2 | | | | | SM00071 | | 9 | | 050-099 |
| 151 | 20 | | PA | 10-0 | 25-53-14 | D01230 | | 1 | | | | | SM00041 | | 9 | | 150-199, 275-299 |
| 152 | 20 | | PA | 6-0 | 25-53-14 | D01240 | | 1 | | | | | SM00072 | | 9 | | 050-099 |
| 152 | 20 | | PA | 10-0 | 25-53-14 | D01230 | | 2 | | | | | SM00042 | | 9 | | 150-199, 275-299 |
| 153 | 20 | | PA | 11-0 | 25-53-14 | D01240 | | 3 | | | | | GD00202 | D.. | 2 | | 050-099 |
| 153 | 20 | | PA | 21-0 | 25-53-14 | D01230 | | 3 | | | | | GD04320 | D.. | 2 | | 150-199, 275-299 |
| 155 | 18 | | PA | 24-0 | 25-53-12 | D01230 | | 5 | DK | | | | GD04322 | A.. | 2 | | 050-099 |
| 155 | 18 | | PA | 23-0 | 25-53-12 | D01234 | | 5 | DK | | | | GD04322 | A.. | 2 | | 150-199, 275-299 |
| 156 | 20 | | PA | 6-0 | 25-53-14 | D01240 | | 6 | | | | | SM00076 | | 9 | | 050-099 |
| 156 | 20 | | PA | 10-0 | 25-53-14 | D01230 | | 6 | | | | | SM00053 | | 9 | | 150-199, 275-299 |
| 158 | 20 | | PA | 24-0 | 25-53-12 | D01230 | | 8 | | | | | GD04322 | S.. | 2 | | 050-099 |
| 158 | 20 | | PA | 23-0 | 25-53-12 | D01234 | | 8 | | | | | GD04322 | S.. | 2 | | 150-199, 275-299 |
| 159 | 20 | | PA | 24-0 | 25-53-12 | D01230 | | 9 | | | | | GD04322 | S.. | 2 | | 050-099 |
| 159 | 20 | | PA | 23-0 | 25-53-12 | D01234 | | 9 | | | | | GD04322 | S.. | 2 | | 150-199, 275-299 |
| 161 | 20 | | PA | 24-0 | 25-53-14 | D01236 | | 1 | | | | | SM00061 | | 9 | | 050-099 |
| 161 | 20 | | PA | 26-0 | 25-53-14 | D11094 | | 1 | | | | | SM00068 | | 9 | | 150-199, 275-299 |
| 162 | 20 | | PA | 24-0 | 25-53-14 | D01236 | | 2 | | | | | SM00062 | | 9 | | 050-099 |
| 162 | 20 | | PA | 26-0 | 25-53-14 | D11094 | | 2 | | | | | SM00069 | | 9 | | 150-199, 275-299 |
| 163 | 20 | | PA | 12-0 | 25-53-14 | D01236 | | 3 | | | | | GD00214 | D.. | 2 | | 050-099 |
| 163 | 20 | | PA | 9-0 | 25-53-14 | D01236 | | 3 | | | | | GD04780 | D.. | 2 | | 150-199, 275-299 |
| 165 | 18 | | PA | 12-0 | 25-53-12 | D01236 | | 5 | DK | | | | GD00214 | A.. | 2 | | 050-099 |
| 165 | 18 | | PA | 21-0 | 25-53-12 | D01230 | | 5 | DK | | | | GD04320 | A.. | 2 | | 150-199, 275-299 |
| 166 | 20 | | PA | 24-0 | 25-53-14 | D01236 | | 6 | | | | | SM00066 | | 9 | | 050-099 |
| 166 | 20 | | PA | 9-0 | 25-53-14 | D01236 | | 6 | | | | | GD04780 | A.. | 2 | | 150-199, 275-299 |
| 168 | 20 | | PA | 12-0 | 25-53-12 | D01236 | | 8 | | | | | GD00214 | S.. | 2 | | 050-099 |
| 168 | 20 | | PA | 21-0 | 25-53-12 | D01230 | | 8 | | | | | GD04320 | S.. | 2 | | 150-199, 275-299 |
| 169 | 20 | | PA | 12-0 | 25-53-12 | D01236 | | 9 | | | | | GD00214 | S.. | 2 | | 050-099 |
| 169 | 20 | | PA | 21-0 | 25-53-12 | D01230 | | 9 | | | | | GD04320 | S.. | 2 | | 150-199, 275-299 |
| 171 | 20 | | PA | 28-0 | 25-53-14 | D01234 | | 1 | | | | | SM00072 | | 9 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0700
Page 10
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | | |
| 171 | 20 | | PA | 27-0 | 25-53-14 | D01240 | | 2 | | | | | SM00072 | | 9 | | 150-199, 275-299 |
| 172 | 20 | | PA | 28-0 | 25-53-14 | D01234 | | 2 | | | | | SM00071 | | 9 | | 050-099 |
| 172 | 20 | | PA | 27-0 | 25-53-14 | D01240 | | 1 | | | | | SM00075 | | 9 | | 150-199, 275-299 |
| 173 | 20 | | PA | 10-0 | 25-53-14 | D01234 | | 3 | | | | | GD00252 | D.. | 2 | | 050-099 |
| 173 | 20 | | PA | 11-0 | 25-53-14 | D01240 | | 3 | | | | | GD00252 | D.. | 2 | | 150-199, 275-299 |
| 175 | 18 | | PA | 11-0 | 25-53-12 | D01240 | | 5 | DK | | | | GD00202 | A.. | 2 | | 050-099 |
| 175 | 18 | | PA | 8-0 | 25-53-12 | D11098 | | 5 | DK | | | | GD04760 | A.. | 2 | | 150-199, 275-299 |
| 176 | 20 | | PA | 28-0 | 25-53-14 | D01234 | | 6 | | | | | SM00076 | | 9 | | 050-099 |
| 176 | 20 | | PA | 27-0 | 25-53-14 | D01240 | | 6 | | | | | SM00076 | | 9 | | 150-199, 275-299 |
| 178 | 20 | | PA | 11-0 | 25-53-12 | D01240 | | 8 | | | | | GD00202 | S.. | 2 | | 050-099 |
| 178 | 20 | | PA | 8-0 | 25-53-12 | D11098 | | 8 | | | | | GD04760 | S.. | 2 | | 150-199, 275-299 |
| 179 | 20 | | PA | 11-0 | 25-53-12 | D01240 | | 9 | | | | | GD00202 | S.. | 2 | | 050-099 |
| 179 | 20 | | PA | 8-0 | 25-53-12 | D11098 | | 9 | | | | | GD04760 | S.. | 2 | | 150-199, 275-299 |
| 181 | 20 | | PA | 55-0 | 25-53-14 | D01226 | | 1 | | | | | D05224P | | 31 | | 050-099 |
| 181 | 20 | | PA | 64-0 | 25-53-14 | D01244 | | 1 | | | | | D05224P | | 3 | | 150-199, 275-299 |
| 182 | 20 | | PA | 55-0 | 25-53-14 | D01226 | | 2 | | | | | D05224P | | 32 | | 050-099 |
| 182 | 20 | | PA | 64-0 | 25-53-14 | D01244 | | 2 | | | | | D05224P | | 6 | | 150-199, 275-299 |
| 183 | 20 | | PA | 24-0 | 25-53-14 | D01226 | | 3 | | | | | GD04394 | D.. | 2 | | 050-099 |
| 183 | 20 | | PA | 8-0 | 25-53-14 | D01244 | | 3 | | | | | GD04764 | D.. | 2 | | 150-199, 275-299 |
| 185 | 18 | | PA | 23-0 | 25-53-12 | D01244 | | 5 | DK | | | | GD04322 | A.. | 2 | | 050-099 |
| 185 | 18 | | PA | 7-0 | 25-53-12 | D11580 | | 5 | DK | | | | GD00280 | A.. | 2 | | 150-199, 275-299 |
| 186 | 20 | | PA | 24-0 | 25-53-14 | D01226 | | 6 | | | | | GD04394 | A.. | 2 | | 050-099 |
| 186 | 20 | | PA | 8-0 | 25-53-14 | D01244 | | 6 | | | | | GD04764 | A.. | 2 | | 150-199, 275-299 |
| 188 | 20 | | PA | 23-0 | 25-53-12 | D01244 | | 8 | | | | | GD04322 | S.. | 2 | | 050-099 |
| 188 | 20 | | PA | 7-0 | 25-53-12 | D11580 | | 8 | | | | | GD00280 | S.. | 2 | | 150-199, 275-299 |
| 189 | 20 | | PA | 23-0 | 25-53-12 | D01244 | | 9 | | | | | GD04322 | S.. | 2 | | 050-099 |
| 189 | 20 | | PA | 7-0 | 25-53-12 | D11580 | | 9 | | | | | GD00280 | S.. | 2 | | 150-199, 275-299 |
| 191 | 20 | | PA | 11-0 | 25-53-14 | D01248 | | 2 | | | | | SM00041 | | 9 | | 150-199, 275-299 |
| 192 | 20 | | PA | 11-0 | 25-53-14 | D01248 | | 1 | | | | | SM00042 | | 9 | | 150-199, 275-299 |
| 193 | 20 | | PA | 23-0 | 25-53-14 | D01248 | | 3 | | | | | GD04322 | D.. | 2 | | 150-199, 275-299 |
| 195 | 18 | | PA | 22-0 | 25-53-12 | D01248 | | 5 | DK | | | | GD04320 | A.. | 2 | | 050-099 |
| 195 | 18 | | PA | 20-0 | 25-53-12 | D01226 | | 5 | DK | | | | GD04322 | A.. | 2 | | 150-199, 275-299 |
| 196 | 20 | | PA | 11-0 | 25-53-14 | D01248 | | 6 | | | | | SM00053 | | 9 | | 150-199, 275-299 |
| 198 | 20 | | PA | 22-0 | 25-53-12 | D01248 | | 8 | | | | | GD04320 | S.. | 2 | | 050-099 |
| 198 | 20 | | PA | 20-0 | 25-53-12 | D01226 | | 8 | | | | | GD04322 | S.. | 2 | | 150-199, 275-299 |
| 199 | 20 | | PA | 22-0 | 25-53-12 | D01248 | | 9 | | | | | GD04320 | S.. | 2 | | 050-099 |
| 199 | 20 | | PA | 20-0 | 25-53-12 | D01226 | | 9 | | | | | GD04322 | S.. | 2 | | 150-199, 275-299 |
| 301B | 20 | | PC | AA | 27-0 | 25-53-12 | D05220P | | 1 | | | | SM00014 | | 9 | | 050-099 |
| 301B | 20 | | PC | AA | 26-0 | 25-53-12 | D05220P | | 1 | | | | SM00014 | | 9 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | |
| 301R | 20 | PC | AA | 0-0 | 25-53-12 | D05220P | | 2 | | | SM00017 | | 9 | | ALL |
| 301Y | 20 | PC | AA | 0-0 | 25-53-12 | D05220P | | 3 | | | SM00010 | | 9 | | ALL |
| 302B | 20 | PC | AB | 22-0 | 25-53-12 | D05220P | | 4 | | | SM00024 | | 9 | | ALL |
| 302R | 20 | PC | AB | 0-0 | 25-53-12 | D05220P | | 5 | | | SM00027 | | 9 | | ALL |
| 302Y | 20 | PC | AB | 0-0 | 25-53-12 | D05220P | | 6 | | | SM00020 | | 9 | | ALL |
| 303B | 20 | PC | AC | 20-0 | 25-53-12 | D05220P | | 7 | | | SM00034 | | 9 | | 050-099 |
| 303B | 20 | PC | AC | 19-0 | 25-53-12 | D05220P | | 7 | | | SM00034 | | 9 | | 150-199, 275-299 |
| 303R | 20 | PC | AC | 0-0 | 25-53-12 | D05220P | | 8 | | | SM00037 | | 9 | | ALL |
| 303Y | 20 | PC | AC | 0-0 | 25-53-12 | D05220P | | 9 | | | SM00030 | | 9 | | ALL |
| 304B | 20 | PC | AD | 21-0 | 25-53-12 | D05220P | | 11 | | | SM00044 | | 9 | | ALL |
| 304R | 20 | PC | AD | 0-0 | 25-53-12 | D05220P | | 12 | | | SM00047 | | 9 | | ALL |
| 304Y | 20 | PC | AD | 0-0 | 25-53-12 | D05220P | | 13 | | | SM00040 | | 9 | | ALL |
| 305B | 20 | PC | AE | 36-0 | 25-53-12 | D05222P | | 1 | | | SM00114 | | 9 | | 050-099 |
| 305B | 20 | PC | AE | 19-0 | 25-53-12 | D05222P | | 1 | | | SM00114 | | 9 | | 150-199, 275-299 |
| 305R | 20 | PC | AE | 0-0 | 25-53-12 | D05222P | | 2 | | | SM00117 | | 9 | | ALL |
| 305Y | 20 | PC | AE | 0-0 | 25-53-12 | D05222P | | 3 | | | SM00110 | | 9 | | ALL |
| 306B | 20 | PC | AF | 18-0 | 25-53-12 | D05222P | | 4 | | | SM00124 | | 9 | | ALL |
| 306R | 20 | PC | AF | 0-0 | 25-53-12 | D05222P | | 5 | | | SM00127 | | 9 | | ALL |
| 306Y | 20 | PC | AF | 0-0 | 25-53-12 | D05222P | | 6 | | | SM00120 | | 9 | | ALL |
| 307B | 20 | PC | AG | 17-0 | 25-53-12 | D05222P | | 7 | | | SM00134 | | 9 | | 050-099 |
| 307B | 20 | PC | AG | 16-0 | 25-53-12 | D05222P | | 7 | | | SM00134 | | 9 | | 150-199, 275-299 |
| 307R | 20 | PC | AG | 0-0 | 25-53-12 | D05222P | | 8 | | | SM00137 | | 9 | | ALL |
| 307Y | 20 | PC | AG | 0-0 | 25-53-12 | D05222P | | 9 | | | SM00130 | | 9 | | ALL |
| 308B | 20 | PC | AH | 23-0 | 25-53-12 | D05222P | | 11 | | | SM00144 | | 9 | | 050-099 |
| 308B | 20 | PC | AH | 16-0 | 25-53-12 | D05222P | | 11 | | | SM00144 | | 9 | | 150-199, 275-299 |
| 308R | 20 | PC | AH | 0-0 | 25-53-12 | D05222P | | 12 | | | SM00147 | | 9 | | ALL |
| 308Y | 20 | PC | AH | 0-0 | 25-53-12 | D05222P | | 13 | | | SM00140 | | 9 | | ALL |
| 311B | 20 | PC | BA | 22-0 | 25-53-12 | D01212 | | 4 | | | SM00014 | | 9 | | 050-099 |
| 311B | 20 | PC | BA | 23-0 | 25-53-12 | D01212 | | 4 | | | SM00014 | | 9 | | 150-199, 275-299 |
| 311R | 20 | PC | BA | 0-0 | 25-53-12 | D01212 | | 7 | | | SM00017 | | 9 | | ALL |
| 311Y | 20 | PC | BA | 0-0 | 25-53-12 | D01212 | | 10 | | | SM00010 | | 9 | | ALL |
| 312B | 20 | PC | BB | 11-0 | 25-53-12 | D01216 | | 4 | | | SM00024 | | 9 | | 050-099 |
| 312B | 20 | PC | BB | 10-0 | 25-53-12 | D11598 | | 4 | | | SM00024 | | 9 | | 150-199, 275-299 |
| 312R | 20 | PC | BB | 0-0 | 25-53-12 | D01216 | | 7 | | | SM00027 | | 9 | | 050-099 |
| 312R | 20 | PC | BB | 0-0 | 25-53-12 | D11598 | | 7 | | | SM00027 | | 9 | | 150-199, 275-299 |
| 312Y | 20 | PC | BB | 0-0 | 25-53-12 | D01216 | | 10 | | | SM00020 | | 9 | | 050-099 |
| 312Y | 20 | PC | BB | 0-0 | 25-53-12 | D11598 | | 10 | | | SM00020 | | 9 | | 150-199, 275-299 |
| 313B | 20 | PC | BC | 6-0 | 25-53-12 | D01220 | | 4 | | | SM00044 | | 9 | | 050-099 |
| 313R | 20 | PC | BC | 0-0 | 25-53-12 | D01220 | | 7 | | | SM00047 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 12

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | |
| 313Y | 20 | PC | BC | 0-0 | 25-53-12 | D01220 | 10 | | | | | | SM00040 | 9 | | 050-099 |
| 314B | 20 | PC | BD | 4-0 | 25-53-12 | D01224 | 4 | | | | | | SM00024 | 9 | | 050-099 |
| 314B | 20 | PC | BD | 19-0 | 25-53-12 | SM00008 | | 9 | | | | | SM00024 | 9 | | 150-199, 275-299 |
| 314R | 20 | PC | BD | 0-0 | 25-53-12 | D01224 | 7 | | | | | | SM00027 | 9 | | 050-099 |
| 314R | 20 | PC | BD | 0-0 | 25-53-12 | SM00009 | | 9 | | | | | SM00027 | 9 | | 150-199, 275-299 |
| 314Y | 20 | PC | BD | 0-0 | 25-53-12 | D01224 | 10 | | | | | | SM00020 | 9 | | 050-099 |
| 314Y | 20 | PC | BD | 0-0 | 25-53-12 | SM00011 | | 9 | | | | | SM00020 | 9 | | 150-199, 275-299 |
| 315B | 20 | PC | BE | 26-0 | 25-53-12 | D01228 | 4 | | | | | | SM00144 | 9 | | 050-099 |
| 315B | 20 | PC | BE | 29-0 | 25-53-12 | D01224 | 4 | | | | | | SM00034 | 9 | | 150-199, 275-299 |
| 315R | 20 | PC | BE | 0-0 | 25-53-12 | D01228 | 7 | | | | | | SM00147 | 9 | | 050-099 |
| 315R | 20 | PC | BE | 0-0 | 25-53-12 | D01224 | 7 | | | | | | SM00037 | 9 | | 150-199, 275-299 |
| 315Y | 20 | PC | BE | 0-0 | 25-53-12 | D01228 | 10 | | | | | | SM00140 | 9 | | 050-099 |
| 315Y | 20 | PC | BE | 0-0 | 25-53-12 | D01224 | 10 | | | | | | SM00030 | 9 | | 150-199, 275-299 |
| 316B | 20 | PC | BF | 20-0 | 25-53-12 | D01232 | 4 | | | | | | SM00014 | 9 | | 050-099 |
| 316B | 20 | PC | BF | 11-0 | 25-53-12 | D01228 | 4 | | | | | | SM00014 | 9 | | 150-199, 275-299 |
| 316R | 20 | PC | BF | 0-0 | 25-53-12 | D01232 | 7 | | | | | | SM00017 | 9 | | 050-099 |
| 316R | 20 | PC | BF | 0-0 | 25-53-12 | D01228 | 7 | | | | | | SM00017 | 9 | | 150-199, 275-299 |
| 316Y | 20 | PC | BF | 0-0 | 25-53-12 | D01232 | 10 | | | | | | SM00010 | 9 | | 050-099 |
| 316Y | 20 | PC | BF | 0-0 | 25-53-12 | D01228 | 10 | | | | | | SM00010 | 9 | | 150-199, 275-299 |
| 317B | 20 | PC | BG | 9-0 | 25-53-12 | D01238 | 4 | | | | | | SM00044 | 9 | | 050-099 |
| 317B | 20 | PC | BG | 7-0 | 25-53-12 | D01220 | 4 | | | | | | SM00044 | 9 | | 150-199, 275-299 |
| 317R | 20 | PC | BG | 0-0 | 25-53-12 | D01238 | 7 | | | | | | SM00047 | 9 | | 050-099 |
| 317R | 20 | PC | BG | 0-0 | 25-53-12 | D01220 | 7 | | | | | | SM00047 | 9 | | 150-199, 275-299 |
| 317Y | 20 | PC | BG | 0-0 | 25-53-12 | D01238 | 10 | | | | | | SM00040 | 9 | | 050-099 |
| 317Y | 20 | PC | BG | 0-0 | 25-53-12 | D01220 | 10 | | | | | | SM00040 | 9 | | 150-199, 275-299 |
| 318B | 20 | PC | BH | 29-0 | 25-53-12 | D01242 | 4 | | | | | | SM00024 | 9 | | 050-099 |
| 318B | 20 | PC | BH | 12-0 | 25-53-12 | D11640 | 4 | | | | | | SM00008 | 9 | | 150-199, 275-299 |
| 318R | 20 | PC | BH | 0-0 | 25-53-12 | D01242 | 7 | | | | | | SM00027 | 9 | | 050-099 |
| 318R | 20 | PC | BH | 0-0 | 25-53-12 | D11640 | 7 | | | | | | SM00009 | 9 | | 150-199, 275-299 |
| 318Y | 20 | PC | BH | 0-0 | 25-53-12 | D01242 | 10 | | | | | | SM00020 | 9 | | 050-099 |
| 318Y | 20 | PC | BH | 0-0 | 25-53-12 | D11640 | 10 | | | | | | SM00011 | 9 | | 150-199, 275-299 |
| 319B | 20 | PC | BJ | 5-0 | 25-53-12 | D01246 | 4 | | | | | | SM00044 | 9 | | 050-099 |
| 319B | 20 | PC | BJ | 2-0 | 25-53-12 | SM00021 | | 9 | | | | | SM00044 | 9 | | 150-199, 275-299 |
| 319R | 20 | PC | BJ | 0-0 | 25-53-12 | D01246 | 7 | | | | | | SM00047 | 9 | | 050-099 |
| 319R | 20 | PC | BJ | 0-0 | 25-53-12 | SM00022 | | 9 | | | | | SM00047 | 9 | | 150-199, 275-299 |
| 319Y | 20 | PC | BJ | 0-0 | 25-53-12 | D01246 | 10 | | | | | | SM00040 | 9 | | 050-099 |
| 319Y | 20 | PC | BJ | 0-0 | 25-53-12 | SM00023 | | 9 | | | | | SM00040 | 9 | | 150-199, 275-299 |
| 320B | 20 | PC | BK | 28-0 | 25-53-12 | D01250 | 4 | | | | | | SM00014 | 9 | | 050-099 |
| 320B | 20 | PC | BK | 4-0 | 25-53-12 | D01250 | 4 | | | | | | SM00014 | 9 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | |
| 320R | 20 | PC | BK | 0-0 | 25-53-12 | D01250 | | 7 | | | SM00017 | | 9 | | ALL |
| 320Y | 20 | PC | BK | 0-0 | 25-53-12 | D01250 | | 10 | | | SM00010 | | 9 | | ALL |
| 321B | 20 | PC | CA | 35-0 | 25-53-12 | D01214 | | 4 | | | SM00114 | | 9 | | 050-099 |
| 321B | 20 | PC | CA | 18-0 | 25-53-12 | D01214 | | 4 | | | SM00114 | | 9 | | 150-199, 275-299 |
| 321R | 20 | PC | CA | 0-0 | 25-53-12 | D01214 | | 7 | | | SM00117 | | 9 | | ALL |
| 321Y | 20 | PC | CA | 0-0 | 25-53-12 | D01214 | | 10 | | | SM00110 | | 9 | | ALL |
| 322B | 20 | PC | CB | 12-0 | 25-53-12 | D01218 | | 4 | | | SM00124 | | 9 | | 050-099 |
| 322B | 20 | PC | CB | 11-0 | 25-53-12 | D01218 | | 4 | | | SM00124 | | 9 | | 150-199, 275-299 |
| 322R | 20 | PC | CB | 0-0 | 25-53-12 | D01218 | | 7 | | | SM00127 | | 9 | | ALL |
| 322Y | 20 | PC | CB | 0-0 | 25-53-12 | D01218 | | 10 | | | SM00120 | | 9 | | ALL |
| 323B | 20 | PC | CC | 7-0 | 25-53-12 | D01222 | | 4 | | | SM00134 | | 9 | | 050-099 |
| 323B | 20 | PC | CC | 8-0 | 25-53-12 | D01222 | | 4 | | | SM00134 | | 9 | | 150-199, 275-299 |
| 323R | 20 | PC | CC | 0-0 | 25-53-12 | D01222 | | 7 | | | SM00137 | | 9 | | ALL |
| 323Y | 20 | PC | CC | 0-0 | 25-53-12 | D01222 | | 10 | | | SM00130 | | 9 | | ALL |
| 324B | 20 | PC | CD | 39-0 | 25-53-12 | D01226 | | 4 | | | SM00124 | | 9 | | 050-099 |
| 324B | 20 | PC | CD | 23-0 | 25-53-12 | SM00005 | | | 9 | | SM00124 | | 9 | | 150-199, 275-299 |
| 324R | 20 | PC | CD | 0-0 | 25-53-12 | D01226 | | 7 | | | SM00127 | | 9 | | 050-099 |
| 324R | 20 | PC | CD | 0-0 | 25-53-12 | SM00006 | | | 9 | | SM00127 | | 9 | | 150-199, 275-299 |
| 324Y | 20 | PC | CD | 0-0 | 25-53-12 | D01226 | | 10 | | | SM00120 | | 9 | | 050-099 |
| 324Y | 20 | PC | CD | 0-0 | 25-53-12 | SM00007 | | | 9 | | SM00120 | | 9 | | 150-199, 275-299 |
| 325B | 20 | PC | CE | 13-0 | 25-53-12 | D01230 | | 4 | | | SM00134 | | 9 | | 050-099 |
| 325B | 20 | PC | CE | 25-0 | 25-53-12 | SM00012 | | | 9 | | SM00134 | | 9 | | 150-199, 275-299 |
| 325R | 20 | PC | CE | 0-0 | 25-53-12 | D01230 | | 7 | | | SM00137 | | 9 | | 050-099 |
| 325R | 20 | PC | CE | 0-0 | 25-53-12 | SM00013 | | | 9 | | SM00137 | | 9 | | 150-199, 275-299 |
| 325Y | 20 | PC | CE | 0-0 | 25-53-12 | D01230 | | 10 | | | SM00130 | | 9 | | 050-099 |
| 325Y | 20 | PC | CE | 0-0 | 25-53-12 | SM00015 | | | 9 | | SM00130 | | 9 | | 150-199, 275-299 |
| 326B | 20 | PC | CF | 16-0 | 25-53-12 | D01236 | | 4 | | | SM00114 | | 9 | | 050-099 |
| 326B | 20 | PC | CF | 9-0 | 25-53-12 | D01230 | | 4 | | | SM00114 | | 9 | | 150-199, 275-299 |
| 326R | 20 | PC | CF | 0-0 | 25-53-12 | D01236 | | 7 | | | SM00117 | | 9 | | 050-099 |
| 326R | 20 | PC | CF | 0-0 | 25-53-12 | D01230 | | 7 | | | SM00117 | | 9 | | 150-199, 275-299 |
| 326Y | 20 | PC | CF | 0-0 | 25-53-12 | D01236 | | 10 | | | SM00110 | | 9 | | 050-099 |
| 326Y | 20 | PC | CF | 0-0 | 25-53-12 | D01230 | | 10 | | | SM00110 | | 9 | | 150-199, 275-299 |
| 327B | 20 | PC | CG | 7-0 | 25-53-12 | D01240 | | 4 | | | SM00144 | | 9 | | 050-099 |
| 327B | 20 | PC | CG | 35-0 | 25-53-12 | D11098 | | 4 | | | SM00016 | | 9 | | 150-199, 275-299 |
| 327R | 20 | PC | CG | 0-0 | 25-53-12 | D01240 | | 7 | | | SM00147 | | 9 | | 050-099 |
| 327R | 20 | PC | CG | 0-0 | 25-53-12 | D11098 | | 7 | | | SM00018 | | 9 | | 150-199, 275-299 |
| 327Y | 20 | PC | CG | 0-0 | 25-53-12 | D01240 | | 10 | | | SM00140 | | 9 | | 050-099 |
| 327Y | 20 | PC | CG | 0-0 | 25-53-12 | D11098 | | 10 | | | SM00019 | | 9 | | 150-199, 275-299 |
| 328B | 20 | PC | CH | 11-0 | 25-53-12 | D01244 | | 4 | | | SM00124 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11
 Section W0700
 Page 14
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|--|-------|------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0704 | 286T0704 | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | | |
| 328B | 20 | PC | NC | 31-0 | 25-53-12 | D11580 | | 4 | | | | | SM00005 | 9 | 150-199, 275-299 |
| 328R | 20 | PC | CH | 0-0 | 25-53-12 | D01244 | | 7 | | | | | SM00127 | 9 | 050-099 |
| 328R | 20 | PC | NC | 0-0 | 25-53-12 | D11580 | | 7 | | | | | SM00006 | 9 | 150-199, 275-299 |
| 328Y | 20 | PC | CH | 0-0 | 25-53-12 | D01244 | | 10 | | | | | SM00120 | 9 | 050-099 |
| 328Y | 20 | PC | NC | 0-0 | 25-53-12 | D11580 | | 10 | | | | | SM00007 | 9 | 150-199, 275-299 |
| 329B | 20 | PC | CJ | 10-0 | 25-53-12 | D01248 | | 4 | | | | | SM00144 | 9 | 050-099 |
| 329B | 20 | PC | CJ | 27-0 | 25-53-12 | D01234 | | 4 | | | | | SM00012 | 9 | 150-199, 275-299 |
| 329R | 20 | PC | CJ | 0-0 | 25-53-12 | D01248 | | 7 | | | | | SM00147 | 9 | 050-099 |
| 329R | 20 | PC | CJ | 0-0 | 25-53-12 | D01234 | | 7 | | | | | SM00013 | 9 | 150-199, 275-299 |
| 329Y | 20 | PC | CJ | 0-0 | 25-53-12 | D01248 | | 10 | | | | | SM00140 | 9 | 050-099 |
| 329Y | 20 | PC | CJ | 0-0 | 25-53-12 | D01234 | | 10 | | | | | SM00015 | 9 | 150-199, 275-299 |
| 330B | 20 | PC | CK | 25-0 | 25-53-12 | D01252 | | 4 | | | | | SM00114 | 9 | 050-099 |
| 330B | 20 | PC | CK | 11-0 | 25-53-12 | D01252 | | 4 | | | | | SM00114 | 9 | 150-199, 275-299 |
| 330R | 20 | PC | CK | 0-0 | 25-53-12 | D01252 | | 7 | | | | | SM00117 | 9 | ALL |
| 330Y | 20 | PC | CK | 0-0 | 25-53-12 | D01252 | | 10 | | | | | SM00110 | 9 | ALL |
| 331B | 20 | PC | CI | 16-0 | 25-53-12 | D01236 | | 4 | | | | | SM00005 | 9 | 150-199, 275-299 |
| 331R | 20 | PC | CI | 0-0 | 25-53-12 | D01236 | | 7 | | | | | SM00006 | 9 | 150-199, 275-299 |
| 331Y | 20 | PC | CI | 0-0 | 25-53-12 | D01236 | | 10 | | | | | SM00007 | 9 | 150-199, 275-299 |
| 332B | 20 | PC | CL | 14-0 | 25-53-12 | D01232 | | 4 | | | | | SM00008 | 9 | 150-199, 275-299 |
| 332R | 20 | PC | CL | 0-0 | 25-53-12 | D01232 | | 7 | | | | | SM00009 | 9 | 150-199, 275-299 |
| 332Y | 20 | PC | CL | 0-0 | 25-53-12 | D01232 | | 10 | | | | | SM00011 | 9 | 150-199, 275-299 |
| 333B | 20 | PC | CM | 16-0 | 25-53-12 | SM00016 | | | 9 | | | | SM00012 | 9 | 150-199, 275-299 |
| 333R | 20 | PC | CM | 0-0 | 25-53-12 | SM00018 | | | 9 | | | | SM00013 | 9 | 150-199, 275-299 |
| 333Y | 20 | PC | CM | 0-0 | 25-53-12 | SM00019 | | | 9 | | | | SM00015 | 9 | 150-199, 275-299 |
| 335B | 20 | PC | CN | 3-0 | 25-53-12 | D01246 | | 4 | | | | | SM00021 | 9 | 150-199, 275-299 |
| 335R | 20 | PC | CN | 0-0 | 25-53-12 | D01246 | | 7 | | | | | SM00022 | 9 | 150-199, 275-299 |
| 335Y | 20 | PC | CN | 0-0 | 25-53-12 | D01246 | | 10 | | | | | SM00023 | 9 | 150-199, 275-299 |
| 336B | 20 | PC | DF | 35-0 | 25-53-12 | D01234 | | 4 | | | | | SM00134 | 9 | 050-099 |
| 336B | 20 | PC | DF | 9-0 | 25-53-12 | D01248 | | 4 | | | | | SM00016 | 9 | 150-199, 275-299 |
| 336R | 20 | PC | DF | 0-0 | 25-53-12 | D01234 | | 7 | | | | | SM00137 | 9 | 050-099 |
| 336R | 20 | PC | DF | 0-0 | 25-53-12 | D01248 | | 7 | | | | | SM00018 | 9 | 150-199, 275-299 |
| 336Y | 20 | PC | DF | 0-0 | 25-53-12 | D01234 | | 10 | | | | | SM00130 | 9 | 050-099 |
| 336Y | 20 | PC | DF | 0-0 | 25-53-12 | D01248 | | 10 | | | | | SM00019 | 9 | 150-199, 275-299 |
| 337B | 20 | PC | DA | 6-0 | 25-53-12 | D01260 | | 4 | | | | | SM00034 | 9 | 050-099 |
| 337R | 20 | PC | DA | 0-0 | 25-53-12 | D01260 | | 7 | | | | | SM00037 | 9 | 050-099 |
| 337Y | 20 | PC | DA | 0-0 | 25-53-12 | D01260 | | 10 | | | | | SM00030 | 9 | 050-099 |
| 338B | 20 | PC | DB | 5-0 | 25-53-12 | D01274 | | 4 | | | | | SM00034 | 9 | 050-099 |
| 338R | 20 | PC | DB | 0-0 | 25-53-12 | D01274 | | 7 | | | | | SM00037 | 9 | 050-099 |
| 338Y | 20 | PC | DB | 0-0 | 25-53-12 | D01274 | | 10 | | | | | SM00030 | 9 | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | |
| 339B | 20 | PC | DC | 29-0 | 25-53-12 | D01280 | | 4 | | | | | SM00034 | 9 | | 050-099 |
| 339R | 20 | PC | DC | 0-0 | 25-53-12 | D01280 | | 7 | | | | | SM00037 | 9 | | 050-099 |
| 339Y | 20 | PC | DC | 0-0 | 25-53-12 | D01280 | | 10 | | | | | SM00030 | 9 | | 050-099 |
| 340B | 20 | PC | G | 23-0 | 25-53-12 | SM00144 | | | 9 | | | | SM00025 | 9 | | 150-199, 275-299 |
| 340R | 20 | PC | G | 0-0 | 25-53-12 | SM00147 | | | 9 | | | | SM00026 | 9 | | 150-199, 275-299 |
| 340Y | 20 | PC | G | 0-0 | 25-53-12 | SM00140 | | | 9 | | | | SM00029 | 9 | | 150-199, 275-299 |
| 341B | 20 | PC | B | 14-0 | 25-53-12 | D01240 | | 4 | | | | | SM00025 | 9 | | 150-199, 275-299 |
| 341R | 20 | PC | B | 0-0 | 25-53-12 | D01240 | | 7 | | | | | SM00026 | 9 | | 150-199, 275-299 |
| 341Y | 20 | PC | B | 0-0 | 25-53-12 | D01240 | | 10 | | | | | SM00029 | 9 | | 150-199, 275-299 |
| 342B | 20 | PC | CP | 4-0 | 25-53-12 | D11096 | | 4 | | | | | SM00021 | 9 | | 150-199, 275-299 |
| 342R | 20 | PC | CP | 0-0 | 25-53-12 | D11096 | | 7 | | | | | SM00022 | 9 | | 150-199, 275-299 |
| 342Y | 20 | PC | CP | 0-0 | 25-53-12 | D11096 | | 10 | | | | | SM00023 | 9 | | 150-199, 275-299 |
| 343B | 20 | PC | D | 9-0 | 25-53-12 | D01238 | | 4 | | | | | SM00033 | 9 | | 150-199, 275-299 |
| 343R | 20 | PC | D | 0-0 | 25-53-12 | D01238 | | 7 | | | | | SM00035 | 9 | | 150-199, 275-299 |
| 343Y | 20 | PC | D | 0-0 | 25-53-12 | D01238 | | 10 | | | | | SM00038 | 9 | | 150-199, 275-299 |
| 344B | 20 | PC | C | 26-0 | 25-53-12 | D11094 | | 4 | | | | | SM00025 | 9 | | 150-199, 275-299 |
| 344R | 20 | PC | C | 0-0 | 25-53-12 | D11094 | | 7 | | | | | SM00026 | 9 | | 150-199, 275-299 |
| 344Y | 20 | PC | C | 0-0 | 25-53-12 | D11094 | | 10 | | | | | SM00029 | 9 | | 150-199, 275-299 |
| 345B | 20 | PC | A | 11-0 | 25-53-12 | D01226 | | 4 | | | | | SM00144 | 9 | | 150-199, 275-299 |
| 345R | 20 | PC | A | 0-0 | 25-53-12 | D01226 | | 7 | | | | | SM00147 | 9 | | 150-199, 275-299 |
| 345Y | 20 | PC | A | 0-0 | 25-53-12 | D01226 | | 10 | | | | | SM00140 | 9 | | 150-199, 275-299 |
| 346B | 20 | PC | F | 35-0 | 25-53-12 | D11092 | | 4 | | | | | SM00033 | 9 | | 150-199, 275-299 |
| 346R | 20 | PC | F | 0-0 | 25-53-12 | D11092 | | 7 | | | | | SM00035 | 9 | | 150-199, 275-299 |
| 346Y | 20 | PC | F | 0-0 | 25-53-12 | D11092 | | 10 | | | | | SM00038 | 9 | | 150-199, 275-299 |
| 347B | 20 | PC | E | 18-0 | 25-53-12 | SM00034 | | | 9 | | | | SM00033 | 9 | | 150-199, 275-299 |
| 347R | 20 | PC | E | 0-0 | 25-53-12 | SM00037 | | | 9 | | | | SM00035 | 9 | | 150-199, 275-299 |
| 347Y | 20 | PC | E | 0-0 | 25-53-12 | SM00030 | | | 9 | | | | SM00038 | 9 | | 150-199, 275-299 |
| 348B | 20 | PC | NW | 47-0 | 25-53-12 | D01244 | | 4 | | | | | SM00114 | 9 | | 150-199, 275-299 |
| 348R | 20 | PC | NW | 0-0 | 25-53-12 | D01244 | | 7 | | | | | SM00117 | 9 | | 150-199, 275-299 |
| 348Y | 20 | PC | NW | 0-0 | 25-53-12 | D01244 | | 10 | | | | | SM00110 | 9 | | 150-199, 275-299 |
| 349B | 20 | PC | NX | 49-0 | 25-53-12 | D01242 | | 4 | | | | | SM00014 | 9 | | 150-199, 275-299 |
| 349R | 20 | PC | NX | 0-0 | 25-53-12 | D01242 | | 7 | | | | | SM00017 | 9 | | 150-199, 275-299 |
| 349Y | 20 | PC | NX | 0-0 | 25-53-12 | D01242 | | 10 | | | | | SM00010 | 9 | | 150-199, 275-299 |
| 350B | 20 | PC | NY | 54-0 | 25-53-12 | D01216 | | 4 | | | | | SM00024 | 9 | | 150-199, 275-299 |
| 350R | 20 | PC | NY | 0-0 | 25-53-12 | D01216 | | 7 | | | | | SM00027 | 9 | | 150-199, 275-299 |
| 350Y | 20 | PC | NY | 0-0 | 25-53-12 | D01216 | | 10 | | | | | SM00020 | 9 | | 150-199, 275-299 |
| 351B | 20 | PC | OA | 33-0 | 25-53-12 | D11578 | | 4 | | | | | SM00124 | 9 | | 150-199, 275-299 |
| 351R | 20 | PC | OA | 0-0 | 25-53-12 | D11578 | | 7 | | | | | SM00127 | 9 | | 150-199, 275-299 |
| 351Y | 20 | PC | OA | 0-0 | 25-53-12 | D11578 | | 10 | | | | | SM00120 | 9 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | | |
| 352B | 20 | PC | OB | 35-0 | 25-53-12 | D11638 | | 4 | | | | | SM00044 | | 9 | | 150-199, 275-299 |
| 352R | 20 | PC | OB | 0-0 | 25-53-12 | D11638 | | 7 | | | | | SM00047 | | 9 | | 150-199, 275-299 |
| 352Y | 20 | PC | OB | 0-0 | 25-53-12 | D11638 | | 10 | | | | | SM00040 | | 9 | | 150-199, 275-299 |
| 501 | 20 | PA | | 9-0 | 25-53-14 | D05224P | | 11 | | | | | SM00001 | | 9 | | 050-099 |
| 502 | 20 | PA | | 9-0 | 25-53-14 | D05224P | | 12 | | | | | SM00002 | | 9 | | 050-099 |
| 503 | 20 | PA | | 9-0 | 25-53-14 | D05224P | | 7 | | | | | SM00003 | | 9 | | 050-099 |
| 504 | 20 | PA | | 14-0 | 25-53-14 | D01222 | | 2 | | | | | SM00002 | | 9 | | 050-099 |
| 505 | 20 | PA | | 14-0 | 25-53-14 | D01222 | | 1 | | | | | SM00001 | | 9 | | 050-099 |
| 506 | 20 | PA | | 17-0 | 25-53-14 | D01222 | | 6 | | | | | GD00322 | A.. | 2 | | 050-099 |
| 507 | 20 | PA | | 17-0 | 25-53-14 | D01222 | | 3 | | | | | GD00322 | D.. | 2 | | 050-099 |
| 508 | 20 | PA | | 9-0 | 25-53-14 | D05224P | | 8 | | | | | SM00004 | | 9 | | 050-099 |
| 509 | 20 | PA | | 11-0 | 25-53-14 | D01260 | | 1 | | | | | SM00003 | | 9 | | 050-099 |
| 510 | 20 | PA | | 15-0 | 25-53-14 | D01260 | | 3 | | | | | GD00322 | D.. | 2 | | 050-099 |
| 511 | 20 | PA | | 11-0 | 25-53-14 | D01260 | | 2 | | | | | SM00004 | | 9 | | 050-099 |
| 512 | 20 | PA | | 15-0 | 25-53-14 | D01260 | | 6 | | | | | GD00322 | A.. | 2 | | 050-099 |
| 513 | 18 | PA | | 15-0 | 25-53-12 | D01260 | | 5 | DK | | | | GD00322 | A.. | 2 | | 050-099 |
| 514 | 20 | PA | | 15-0 | 25-53-12 | D01260 | | 8 | | | | | GD00322 | S.. | 2 | | 050-099 |
| 515 | 20 | PA | | 15-0 | 25-53-12 | D01260 | | 9 | | | | | GD00322 | S.. | 2 | | 050-099 |
| 516 | 20 | PA | | 21-0 | 25-53-14 | D05224P | | 13 | | | | | D01274 | | 1 | | 050-099 |
| 517 | 20 | PA | | 21-0 | 25-53-14 | D05224P | | 29 | | | | | D01274 | | 2 | | 050-099 |
| 518 | 20 | PA | | 17-0 | 25-53-14 | D01274 | | 3 | | | | | GD04320 | D.. | 2 | | 050-099 |
| 519 | 20 | PA | | 21-0 | 25-53-14 | D01274 | | 6 | | | | | D05224P | | 33 | | 050-099 |
| 520 | 20 | PA | | 18-0 | 25-53-14 | D05224P | | 16 | | | | | SM00046 | | 9 | | 050-099 |
| 521 | 20 | PA | | 19-0 | 25-53-14 | D05224P | | 19 | | | | | SM00036 | | 9 | | 050-099 |
| 522 | 20 | PA | | 22-0 | 25-53-14 | D05224P | | 6 | | | | | SM00102 | | 9 | | 050-099 |
| 523 | 20 | PA | | 22-0 | 25-53-14 | D05224P | | 3 | | | | | SM00101 | | 9 | | 050-099 |
| 524 | 20 | PA | | 22-0 | 25-53-14 | D05224P | | 9 | | | | | SM00106 | | 9 | | 050-099 |
| 525 | 20 | PA | | 4-0 | 25-53-14 | D01224 | | 2 | | | | | SM00102 | | 9 | | 050-099 |
| 526 | 20 | PA | | 4-0 | 25-53-14 | D01224 | | 1 | | | | | SM00101 | | 9 | | 050-099 |
| 527 | 20 | PA | | 4-0 | 25-53-14 | D01224 | | 6 | | | | | SM00106 | | 9 | | 050-099 |
| 528 | 20 | PA | | 21-0 | 25-53-14 | D01224 | | 3 | | | | | GD04326 | D.. | 2 | | 050-099 |
| 529 | 20 | PA | | 18-0 | 25-53-14 | D01246 | | 3 | | | | | GD04320 | D.. | 2 | | 050-099 |
| 530 | 20 | PA | | 6-0 | 25-53-14 | D01246 | | 1 | | | | | SM00102 | | 9 | | 050-099 |
| 531 | 20 | PA | | 19-0 | 25-53-14 | D05224P | | 14 | | | | | SM00031 | | 9 | | ALL |
| 532 | 20 | PA | | 19-0 | 25-53-14 | D05224P | | 15 | | | | | SM00032 | | 9 | | ALL |
| 533 | 20 | PA | | 6-0 | 25-53-14 | D01246 | | 2 | | | | | SM00101 | | 9 | | 050-099 |
| 534 | 20 | PA | | 6-0 | 25-53-14 | D01246 | | 6 | | | | | SM00106 | | 9 | | 050-099 |
| 535 | 18 | PA | | 17-0 | 25-53-12 | D01274 | | 5 | DK | | | | GD04320 | A.. | 2 | | 050-099 |
| 536 | 20 | PA | | 17-0 | 25-53-12 | D01274 | | 8 | | | | | GD04320 | S.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 17

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|-----|---|--|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | | | | |
| 537 | 20 | | PA | | 17-0 | 25-53-12 | D01274 | | | | 9 | | | | GD04320 | S.. | 2 | | 050-099 |
| 538 | 18 | | PA | | 7-0 | 25-53-12 | D01280 | | | | 5 | DK | | | GD00252 | A.. | 2 | | 050-099 |
| 539 | 20 | | PA | | 7-0 | 25-53-12 | D01280 | | | | 8 | | | | GD00252 | S.. | 2 | | 050-099 |
| 540 | 20 | | PA | | 7-0 | 25-53-12 | D01280 | | | | 9 | | | | GD00252 | S.. | 2 | | 050-099 |
| 541 | 20 | | PA | | 18-0 | 25-53-14 | D05224P | | | | 17 | | | | SM00041 | | 9 | | ALL |
| 542 | 20 | | PA | | 18-0 | 25-53-14 | D05224P | | | | 18 | | | | SM00042 | | 9 | | ALL |
| 543 | 20 | | PA | | 9-0 | 25-53-14 | D05224P | | | | 12 | | | | SM00039 | | 9 | | 150-199, 275-299 |
| 544 | 20 | | PA | | 15-0 | 25-53-14 | D05224P | | | | 11 | | | | SM00048 | | 9 | | 150-199, 275-299 |
| 545 | 20 | | PA | | 9-0 | 25-53-14 | D05224P | | | | 8 | | | | SM00045 | | 9 | | 150-199, 275-299 |
| 546 | 20 | | PA | | 9-0 | 25-53-14 | D05224P | | | | 7 | | | | SM00043 | | 9 | | 150-199, 275-299 |
| 547 | 20 | | PA | | 18-0 | 25-53-14 | D05224P | | | | 36 | | | | SM00053 | | 9 | | 150-199, 275-299 |
| 548 | 20 | | PA | | 11-0 | 25-53-14 | D05224P | | | | 45 | | | | SM00058 | | 9 | | 150-199, 275-299 |
| 549 | 20 | | PA | | 25-0 | 25-53-14 | D11578 | | | | 2 | | | | SM00062 | | 9 | | 150-199, 275-299 |
| 550 | 20 | | PA | | 25-0 | 25-53-14 | D11578 | | | | 1 | | | | SM00061 | | 9 | | 150-199, 275-299 |
| 551 | 20 | | PA | | 25-0 | 25-53-14 | D05224P | | | | 21 | | | | SM00051 | | 9 | | ALL |
| 552 | 20 | | PA | | 25-0 | 25-53-14 | D05224P | | | | 22 | | | | SM00052 | | 9 | | ALL |
| 553 | 20 | | PA | | 49-0 | 25-53-14 | D11638 | | | | 6 | | | | GD04320 | A.. | 2 | | 150-199, 275-299 |
| 554 | 20 | | PA | | 31-0 | 25-53-14 | D11638 | | | | 1 | | | | SM00071 | | 9 | | 150-199, 275-299 |
| 555 | 20 | | PA | | 31-0 | 25-53-14 | D11638 | | | | 2 | | | | SM00070 | | 9 | | 150-199, 275-299 |
| 556 | 20 | | PA | | 25-0 | 25-53-14 | D05224P | | | | 23 | | | | SM00056 | | 9 | | ALL |
| 557 | 20 | | PA | | 14-0 | 25-53-14 | D11640 | | | | 6 | | | | GD04780 | A.. | 2 | | 150-199, 275-299 |
| 558 | 20 | | PA | | 46-0 | 25-53-14 | D11092 | | | | 2 | | | | SM00070 | | 9 | | 150-199, 275-299 |
| 559 | 20 | | PA | | 46-0 | 25-53-14 | D11092 | | | | 1 | | | | SM00071 | | 9 | | 150-199, 275-299 |
| 560 | 20 | | PA | | 8-0 | 25-53-14 | D11094 | | | | 6 | | | | GD04762 | A.. | 2 | | 150-199, 275-299 |
| 561 | 20 | | PA | | 26-0 | 25-53-14 | D05224P | | | | 10 | | | | SM00061 | | 9 | | ALL |
| 562 | 20 | | PA | | 26-0 | 25-53-14 | D05224P | | | | 20 | | | | SM00062 | | 9 | | ALL |
| 563 | 20 | | PA | | 8-0 | 25-53-14 | D11094 | | | | 3 | | | | GD04762 | D.. | 2 | | 150-199, 275-299 |
| 565 | 20 | | PA | | 21-0 | 25-53-14 | D11578 | | | | 3 | | | | GD00384 | D.. | 2 | | 150-199, 275-299 |
| 566 | 20 | | PA | | 26-0 | 25-53-14 | D05224P | | | | 40 | | | | SM00066 | | 9 | | ALL |
| 567 | 20 | | PA | | 49-0 | 25-53-14 | D11638 | | | | 3 | | | | GD04320 | D.. | 2 | | 150-199, 275-299 |
| 568 | 20 | | PA | | 14-0 | 25-53-14 | D11640 | | | | 3 | | | | GD04780 | D.. | 2 | | 150-199, 275-299 |
| 570 | 18 | | PA | | 13-0 | 25-53-12 | D11092 | | | | 5 | DK | | | GD04762 | A.. | 2 | | 150-199, 275-299 |
| 571 | 20 | | PA | | 23-0 | 25-53-14 | D05224P | | | | 24 | | | | SM00071 | | 9 | | 050-099 |
| 571 | 20 | | PA | | 23-0 | 25-53-14 | D05224P | | | | 24 | | | | SM00075 | | 9 | | 150-199, 275-299 |
| 572 | 20 | | PA | | 23-0 | 25-53-14 | D05224P | | | | 25 | | | | SM00072 | | 9 | | ALL |
| 573 | 20 | | PA | | 13-0 | 25-53-12 | D11092 | | | | 8 | | | | GD04762 | S.. | 2 | | 150-199, 275-299 |
| 574 | 20 | | PA | | 13-0 | 25-53-12 | D11092 | | | | 9 | | | | GD04762 | S.. | 2 | | 150-199, 275-299 |
| 576 | 20 | | PA | | 23-0 | 25-53-14 | D05224P | | | | 26 | | | | SM00076 | | 9 | | 050-099 |
| 576 | 20 | | PA | | 24-0 | 25-53-14 | D05224P | | | | 26 | | | | SM00076 | | 9 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11
Section W0700
Page 18
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | |
| 577 | 18 | PA | | 11-0 | 25-53-12 | D01240 | | 5 | DK | | | | GD00252 | A.. | 2 | 150-199, 275-299 |
| 578 | 20 | PA | | 11-0 | 25-53-12 | D01240 | | 8 | | | | | GD00252 | S.. | 2 | 150-199, 275-299 |
| 579 | 20 | PA | | 11-0 | 25-53-12 | D01240 | | 9 | | | | | GD00252 | S.. | 2 | 150-199, 275-299 |
| 580 | 18 | PA | | 8-0 | 25-53-12 | D11094 | | 5 | DK | | | | GD04762 | A.. | 2 | 150-199, 275-299 |
| 581 | 20 | PA | | 48-0 | 25-53-14 | D05224P | | 27 | | | | | D11640 | 1 | | 150-199, 275-299 |
| 582 | 20 | PA | | 48-0 | 25-53-14 | D05224P | | 28 | | | | | D11640 | 2 | | 150-199, 275-299 |
| 583 | 18 | PA | | 5-0 | 25-53-12 | D01238 | | 5 | DK | | | | GD00252 | A.. | 2 | 150-199, 275-299 |
| 584 | 20 | PA | | 5-0 | 25-53-12 | D01238 | | 8 | | | | | GD00252 | S.. | 2 | 150-199, 275-299 |
| 585 | 20 | PA | | 5-0 | 25-53-12 | D01238 | | 9 | | | | | GD00252 | S.. | 2 | 150-199, 275-299 |
| 587 | 20 | PA | | 8-0 | 25-53-12 | D11094 | | 8 | | | | | GD04762 | S.. | 2 | 150-199, 275-299 |
| 588 | 20 | PA | | 8-0 | 25-53-12 | D11094 | | 9 | | | | | GD04762 | S.. | 2 | 150-199, 275-299 |
| 591 | 20 | PA | | 53-0 | 25-53-14 | D05224P | | 31 | | | | | D01236 | 1 | | 150-199, 275-299 |
| 592 | 20 | PA | | 53-0 | 25-53-14 | D05224P | | 32 | | | | | D01236 | 2 | | 150-199, 275-299 |
| 593 | 20 | PA | | 23-0 | 25-53-14 | SM00071 | | | 9 | | | | D05224P | 34 | | 150-199, 275-299 |
| 594 | 20 | PA | | 13-0 | 25-53-14 | D11092 | | 6 | | | | | GD04762 | A.. | 2 | 150-199, 275-299 |
| 595 | 20 | PA | | 23-0 | 25-53-14 | SM00070 | | | 9 | | | | D05224P | 35 | | 150-199, 275-299 |
| 596 | 20 | PA | | 13-0 | 25-53-14 | D11092 | | 3 | | | | | GD04762 | D.. | 2 | 150-199, 275-299 |
| 597 | 20 | PA | | 8-0 | 25-53-14 | D11098 | | 6 | | | | | GD04760 | A.. | 2 | 150-199, 275-299 |
| 598 | 20 | PA | | 23-0 | 25-53-14 | D11098 | | 1 | | | | | SM00068 | 9 | | 150-199, 275-299 |
| 599 | 20 | PA | | 23-0 | 25-53-14 | D11098 | | 2 | | | | | SM00069 | 9 | | 150-199, 275-299 |
| 600 | 20 | PA | | 8-0 | 25-53-14 | D11098 | | 3 | | | | | GD04760 | D.. | 2 | 150-199, 275-299 |
| 601 | 20 | PA | | 8-0 | 25-53-14 | D11096 | | 6 | | | | | SM00053 | 9 | | 150-199, 275-299 |
| 602 | 20 | PA | | 7-0 | 25-53-14 | D11096 | | 1 | | | | | SM00032 | 9 | | 150-199, 275-299 |
| 603 | 20 | PA | | 21-0 | 25-53-14 | D11096 | | 3 | | | | | GD04326 | D.. | 2 | 150-199, 275-299 |
| 604 | 20 | PA | | 7-0 | 25-53-14 | D11096 | | 2 | | | | | SM00031 | 9 | | 150-199, 275-299 |
| 610 | 20 | PA | | 9-0 | 25-53-14 | D11580 | | 6 | | | | | GD04764 | A.. | 2 | 150-199, 275-299 |
| 611 | 20 | PA | | 68-0 | 25-53-14 | D11580 | | 1 | | | | | D05224P | 16 | | 150-199, 275-299 |
| 612 | 20 | PA | | 68-0 | 25-53-14 | D11580 | | 2 | | | | | D05224P | 19 | | 150-199, 275-299 |
| 613 | 20 | PA | | 9-0 | 25-53-14 | D11580 | | 3 | | | | | GD04764 | D.. | 2 | 150-199, 275-299 |
| 614 | 20 | PA | | 11-0 | 25-53-14 | D05224P | | 39 | | | | | SM00065 | 9 | | 150-199, 275-299 |
| 615 | 20 | PA | | 21-0 | 25-53-14 | D05224P | | 41 | | | | | SM00063 | 9 | | 150-199, 275-299 |
| 616 | 20 | PA | | 25-0 | 25-53-14 | D11578 | | 6 | | | | | SM00066 | 9 | | 150-199, 275-299 |
| 617 | 18 | PA | | 13-0 | 25-53-12 | D01242 | | 5 | DK | | | | GD04764 | A.. | 2 | 150-199, 275-299 |
| 618 | 20 | PA | | 13-0 | 25-53-12 | D01242 | | 8 | | | | | GD04764 | S.. | 2 | 150-199, 275-299 |
| 619 | 20 | PA | | 13-0 | 25-53-12 | D01242 | | 9 | | | | | GD04764 | S.. | 2 | 150-199, 275-299 |
| 620 | 18 | PA | | 8-0 | 25-53-12 | D01244 | | 5 | DK | | | | GD04764 | A.. | 2 | 150-199, 275-299 |
| 621 | 20 | PA | | 8-0 | 25-53-12 | D01244 | | 8 | | | | | GD04764 | S.. | 2 | 150-199, 275-299 |
| 622 | 20 | PA | | 8-0 | 25-53-12 | D01244 | | 9 | | | | | GD04764 | S.. | 2 | 150-199, 275-299 |
| 623 | 18 | PA | | 11-0 | 25-53-12 | D01216 | | 5 | DK | | | | GD00280 | A.. | 2 | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 19

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0704 | 286T0704 | | | FWD CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | |
| 624 | 20 | | PA | 11-0 | 25-53-12 | D01216 | | 8 | | | GD00280 | S.. | 2 | | 150-199, 275-299 |
| 625 | 20 | | PA | 11-0 | 25-53-12 | D01216 | | 9 | | | GD00280 | S.. | 2 | | 150-199, 275-299 |
| 626 | 18 | | PA | 13-0 | 25-53-12 | D11578 | | 5 | DK | | GD00214 | A.. | 2 | | 150-199, 275-299 |
| 627 | 20 | | PA | 13-0 | 25-53-12 | D11578 | | 8 | | | GD00214 | S.. | 2 | | 150-199, 275-299 |
| 628 | 20 | | PA | 13-0 | 25-53-12 | D11578 | | 9 | | | GD00214 | S.. | 2 | | 150-199, 275-299 |
| 629 | 18 | | PA | 13-0 | 25-53-12 | D11638 | | 5 | DK | | GD04760 | A.. | 2 | | 150-199, 275-299 |
| 630 | 20 | | PA | 13-0 | 25-53-12 | D11638 | | 8 | | | GD04760 | S.. | 2 | | 150-199, 275-299 |
| 631 | 20 | | PA | 13-0 | 25-53-12 | D11638 | | 9 | | | GD04760 | S.. | 2 | | 150-199, 275-299 |
| 632 | 20 | | PA | 9-0 | 25-53-14 | D11598 | | 1 | | | SM00043 | | 9 | | 150-199, 275-299 |
| 633 | 20 | | PA | 9-0 | 25-53-14 | D11598 | | 2 | | | SM00045 | | 9 | | 150-199, 275-299 |
| 634 | 20 | | PA | 12-0 | 25-53-14 | D11598 | | 3 | | | GD00166 | D.. | 2 | | 150-199, 275-299 |
| 635 | 20 | | PA | 12-0 | 25-53-14 | D11598 | | 6 | | | GD00166 | A.. | 2 | | 150-199, 275-299 |
| 636 | 18 | | PA | 10-0 | 25-53-12 | D01224 | | 5 | DK | | GD00214 | A.. | 2 | | 150-199, 275-299 |
| 637 | 20 | | PA | 10-0 | 25-53-12 | D01224 | | 8 | | | GD00214 | S.. | 2 | | 150-199, 275-299 |
| 638 | 20 | | PA | 10-0 | 25-53-12 | D01224 | | 9 | | | GD00214 | S.. | 2 | | 150-199, 275-299 |
| 639 | 20 | | PA | 7-0 | 25-53-14 | D01252 | | 2 | | | SM00072 | | 9 | | 150-199, 275-299 |
| 640 | 20 | | PA | 7-0 | 25-53-14 | D01252 | | 6 | | | SM00076 | | 9 | | 150-199, 275-299 |
| 661 | 20 | | PA | 22-0 | 25-53-14 | D01228 | | 1 | | | SM00061 | | 9 | | 050-099 |
| 661 | 20 | | PA | 9-0 | 25-53-14 | D01234 | | 1 | | | SM00063 | | 9 | | 150-199, 275-299 |
| 662 | 20 | | PA | 22-0 | 25-53-14 | D01228 | | 2 | | | SM00062 | | 9 | | 050-099 |
| 662 | 20 | | PA | 18-0 | 25-53-14 | D01234 | | 2 | | | SM00058 | | 9 | | 150-199, 275-299 |
| 663 | 20 | | PA | 9-0 | 25-53-14 | D01228 | | 3 | | | GD00214 | D.. | 2 | | 050-099 |
| 663 | 20 | | PA | 23-0 | 25-53-14 | D01234 | | 3 | | | GD04322 | D.. | 2 | | 150-199, 275-299 |
| 665 | 18 | | PA | 10-0 | 25-53-12 | D01234 | | 5 | DK | | GD00252 | A.. | 2 | | 050-099 |
| 665 | 18 | | PA | 23-0 | 25-53-12 | D01248 | | 5 | DK | | GD04322 | A.. | 2 | | 150-199, 275-299 |
| 666 | 20 | | PA | 22-0 | 25-53-14 | D01228 | | 6 | | | SM00066 | | 9 | | 050-099 |
| 666 | 20 | | PA | 18-0 | 25-53-14 | D01234 | | 6 | | | SM00065 | | 9 | | 150-199, 275-299 |
| 668 | 20 | | PA | 10-0 | 25-53-12 | D01234 | | 8 | | | GD00252 | S.. | 2 | | 050-099 |
| 668 | 20 | | PA | 23-0 | 25-53-12 | D01248 | | 8 | | | GD04322 | S.. | 2 | | 150-199, 275-299 |
| 669 | 20 | | PA | 10-0 | 25-53-12 | D01234 | | 9 | | | GD00252 | S.. | 2 | | 050-099 |
| 669 | 20 | | PA | 23-0 | 25-53-12 | D01248 | | 9 | | | GD04322 | S.. | 2 | | 150-199, 275-299 |
| W0706 | 286T0706 | | | AFT CARGO LOADING CONTROL (P27) | | | | | | | | | | | |
| 001 | 20 | | PA | 5-0 | 25-53-21 | D05250P | | 1 | | | D00824 | | 1 | | ALL |
| 002 | 20 | | PA | 5-0 | 25-53-21 | D05250P | | 2 | | | D00824 | | 2 | | ALL |
| 003 | 20 | | PA | 6-0 | 25-53-21 | D05250P | | 3 | | | SP00768 | | 1A | | 050-099 |
| 003 | 20 | | PA | 7-0 | 25-53-21 | D05250P | | 3 | | | SP00768 | | 1A | | 150-199, 275-299 |
| 004 | 20 | | PA | 5-0 | 25-53-23 | D05250P | | 4 | | | D00824 | | 4 | | ALL |
| 005 | 20 | | PA | 5-0 | 25-53-26 | D05250P | | 5 | | | D00824 | | 5 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0700
Page 20
Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0706 | 286T0706 | | | AFT CARGO LOADING CONTROL (P27) (continued) | | | | | | | | | | | |
| 006 | 20 | | PA | | 5-0 | 25-53-26 | D05250P | | 6 | | D00824 | | 6 | | ALL |
| 007 | 20 | | PA | | 5-0 | 25-53-27 | D05250P | | 7 | | D00824 | | 7 | | 050-099, 150-199 |
| 008 | 20 | | PA | | 5-0 | 25-53-27 | D05250P | | 8 | | D00824 | | 8 | | 050-099, 150-199 |
| 011 | 20 | | PA | | 6-0 | 25-53-21 | D05250P | | 11 | | D00822 | | 1 | | ALL |
| 012 | 20 | | PA | | 11-0 | 25-53-21 | GD00330 | S.. | 2 | | D00822 | | 2 | | ALL |
| 013 | 20 | | PA | | 6-0 | 25-53-23 | D05250P | | 13 | | D00822 | | 3 | | ALL |
| 014 | 20 | | PA | | 6-0 | 25-53-24 | D05250P | | 14 | | D00822 | | 4 | | ALL |
| 015 | 20 | | PA | | 6-0 | 25-53-24 | D05250P | | 15 | | D00822 | | 5 | | ALL |
| 016 | 20 | | PA | | 6-0 | 25-53-23 | D05250P | | 16 | | D00822 | | 6 | | ALL |
| 017 | 20 | | PA | | 6-0 | 25-53-23 | D05250P | | 17 | | D00822 | | 7 | | ALL |
| 018 | 20 | | PA | | 6-0 | 25-53-25 | D05250P | | 18 | | D00822 | | 8 | | 050-099 |
| 018 | 20 | | PA | | 6-0 | 25-53-24 | D05250P | | 18 | | D00822 | | 8 | | 150-199, 275-299 |
| 022 | 20 | | PA | | 5-0 | 25-53-26 | D05250P | | 22 | | D00824 | | 15 | | ALL |
| 023 | 20 | | PA | | 5-0 | 25-53-27 | D05250P | | 23 | | D00824 | | 13 | | 050-099, 150-199 |
| 024 | 20 | | PA | | 5-0 | 25-53-27 | D05250P | | 24 | | D00824 | | 14 | | 050-099, 150-199 |
| 033 | 20 | | PA | | 11-0 | 25-53-21 | GD00330 | D.. | 2 | | D00824 | | 3 | | ALL |
| 034 | 20 | | PA | | 11-0 | 25-53-21 | GD00330 | D.. | 2 | | SP00770 | | 1A | | 050-099 |
| 034 | 20 | | PA | | 12-0 | 25-53-21 | GD00330 | D.. | 2 | | SP00770 | | 1A | | 150-199, 275-299 |
| A-A | | | | | 0-0 | 25-53-21 | L00596 | | =1 | | SP00768 | | 1A | | ALL |
| A-B | | | | | 0-0 | 25-53-21 | L00596 | | =2 | | SP00770 | | 1A | | ALL |
| W0708 | 286T0708 | | | AFT CARGO GUIDE ACTUATORS AND DOOR STOPS | | | | | | | | | | | |
| 001 | 20 | | PA | | 6-0 | 25-53-25 | D02318 | | 1 | | GD00382 | A.. | 2 | | ALL |
| 002 | 20 | | PA | | 30-0 | 25-53-25 | D02318 | | 2 | | D05252P | | 1 | | ALL |
| 003 | 20 | | PA | | 30-0 | 25-53-25 | D02318 | | 4 | | D05252P | | 2 | | ALL |
| 004 | 20 | | PA | | 6-0 | 25-53-25 | D02318 | | 12 | | GD00382 | S.. | 2 | | ALL |
| 011 | 20 | | PA | | 7-0 | 25-53-25 | D02320 | | 1 | | GD00382 | A.. | 2 | | 050-099 |
| 011 | 20 | | PA | | 9-0 | 25-53-25 | D02320 | | 1 | | GD00382 | A.. | 2 | | 150-199, 275-299 |
| 012 | 20 | | PA | | 33-0 | 25-53-25 | D02320 | | 2 | | D05252P | | 3 | | ALL |
| 013 | 20 | | PA | | 33-0 | 25-53-25 | D02320 | | 4 | | D05252P | | 4 | | ALL |
| 014 | 20 | | PA | | 7-0 | 25-53-25 | D02320 | | 12 | | GD00382 | S.. | 2 | | 050-099 |
| 014 | 20 | | PA | | 9-0 | 25-53-25 | D02320 | | 12 | | GD00382 | S.. | 2 | | 150-199, 275-299 |
| 021 | 20 | | PA | | 12-0 | 25-53-25 | D02322 | | 1 | | GD00382 | A.. | 2 | | ALL |
| 022 | 20 | | PA | | 36-0 | 25-53-25 | D02322 | | 2 | | D05252P | | 5 | | ALL |
| 023 | 20 | | PA | | 36-0 | 25-53-25 | D02322 | | 4 | | D05252P | | 6 | | ALL |
| 024 | 20 | | PA | | 12-0 | 25-53-25 | D02322 | | 12 | | GD00382 | S.. | 2 | | ALL |
| 031 | 20 | | PA | | 5-0 | 25-53-25 | D02324 | | 1 | | GD00388 | A.. | 2 | | ALL |
| 032 | 20 | | PA | | 33-0 | 25-53-25 | D02324 | | 2 | | D05252P | | 7 | | ALL |
| 033 | 20 | | PA | | 33-0 | 25-53-25 | D02324 | | 4 | | D05252P | | 8 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0700

Page 21

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|-------|------|------|--------|-------------|-----|----|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0708 | 286T0708 | | | AFT CARGO GUIDE ACTUATORS AND DOOR STOPS (continued) | | | | | | | | | | | | | | |
| 034 | 20 | | PA | | 5-0 | 25-53-25 | D02324 | | | | 12 | | | | GD00388 | S.. | 2 | ALL |
| 041 | 20 | | PA | | 9-0 | 25-53-25 | D02326 | | | | 1 | | | | GD00388 | A.. | 2 | ALL |
| 042 | 20 | | PA | | 37-0 | 25-53-25 | D02326 | | | | 2 | | | | D05252P | | 9 | 050-099 |
| 042 | 20 | | PA | | 36-0 | 25-53-25 | D02326 | | | | 2 | | | | D05252P | | 9 | 150-199, 275-299 |
| 043 | 20 | | PA | | 37-0 | 25-53-25 | D02326 | | | | 4 | | | | D05252P | | 10 | 050-099 |
| 043 | 20 | | PA | | 36-0 | 25-53-25 | D02326 | | | | 4 | | | | D05252P | | 10 | 150-199, 275-299 |
| 044 | 20 | | PA | | 9-0 | 25-53-25 | D02326 | | | | 12 | | | | GD00388 | S.. | 2 | ALL |
| 051 | 20 | | PA | | 12-0 | 25-53-25 | D02328 | | | | 1 | | | | GD00388 | A.. | 2 | ALL |
| 052 | 20 | | PA | | 40-0 | 25-53-25 | D02328 | | | | 2 | | | | D05252P | | 11 | 050-099 |
| 052 | 20 | | PA | | 39-0 | 25-53-25 | D02328 | | | | 2 | | | | D05252P | | 11 | 150-199, 275-299 |
| 053 | 20 | | PA | | 40-0 | 25-53-25 | D02328 | | | | 4 | | | | D05252P | | 12 | 050-099 |
| 053 | 20 | | PA | | 39-0 | 25-53-25 | D02328 | | | | 4 | | | | D05252P | | 12 | 150-199, 275-299 |
| 054 | 20 | | PA | | 12-0 | 25-53-25 | D02328 | | | | 12 | | | | GD00388 | S.. | 2 | ALL |
| 061 | 20 | | PA | | 7-0 | 25-53-26 | D02330 | | | | 1 | | | | GD00382 | A.. | 2 | ALL |
| 062 | 20 | | PA | | 32-0 | 25-53-26 | D02334 | | | | 2 | | | | D05252P | | 17 | ALL |
| 063 | 20 | | PA | | 32-0 | 25-53-26 | D02334 | | | | 5 | | | | D05252P | | 18 | ALL |
| 064 | 20 | | PA | | 7-0 | 25-53-26 | D02330 | | | | 12 | | | | GD00382 | S.. | 2 | ALL |
| 071 | 20 | | PA | | 7-0 | 25-53-26 | D02332 | | | | 1 | | | | GD00388 | A.. | 2 | ALL |
| 072 | 20 | | PA | | 34-0 | 25-53-26 | D02332 | | | | 2 | | | | D05252P | | 15 | ALL |
| 073 | 20 | | PA | | 34-0 | 25-53-26 | D02332 | | | | 5 | | | | D05252P | | 16 | ALL |
| 074 | 20 | | PA | | 7-0 | 25-53-26 | D02332 | | | | 12 | | | | GD00388 | S.. | 2 | ALL |
| 081 | 20 | | PA | | 8-0 | 25-53-26 | D02334 | | | | 1 | | | | GD00382 | A.. | 2 | ALL |
| 082 | 20 | | PA | | 33-0 | 25-53-26 | D02330 | | | | 2 | | | | D05252P | | 13 | 050-099 |
| 082 | 20 | | PA | | 31-0 | 25-53-26 | D02330 | | | | 2 | | | | D05252P | | 13 | 150-199, 275-299 |
| 083 | 20 | | PA | | 33-0 | 25-53-26 | D02330 | | | | 5 | | | | D05252P | | 14 | 050-099 |
| 083 | 20 | | PA | | 31-0 | 25-53-26 | D02330 | | | | 5 | | | | D05252P | | 14 | 150-199, 275-299 |
| 084 | 20 | | PA | | 8-0 | 25-53-26 | D02334 | | | | 12 | | | | GD00382 | S.. | 2 | ALL |
| 091 | 20 | | PA | | 10-0 | 25-53-26 | D02336 | | | | 1 | | | | GD00388 | A.. | 2 | 050-099 |
| 091 | 20 | | PA | | 8-0 | 25-53-26 | D02336 | | | | 1 | | | | GD00388 | A.. | 2 | 150-199, 275-299 |
| 092 | 20 | | PA | | 37-0 | 25-53-26 | D02336 | | | | 2 | | | | D05252P | | 19 | 050-099 |
| 092 | 20 | | PA | | 36-0 | 25-53-26 | D02336 | | | | 2 | | | | D05252P | | 19 | 150-199, 275-299 |
| 093 | 20 | | PA | | 37-0 | 25-53-26 | D02336 | | | | 5 | | | | D05252P | | 20 | 050-099 |
| 093 | 20 | | PA | | 36-0 | 25-53-26 | D02336 | | | | 5 | | | | D05252P | | 20 | 150-199, 275-299 |
| 094 | 20 | | PA | | 10-0 | 25-53-26 | D02336 | | | | 12 | | | | GD00388 | S.. | 2 | 050-099 |
| 094 | 20 | | PA | | 8-0 | 25-53-26 | D02336 | | | | 12 | | | | GD00388 | S.. | 2 | 150-199, 275-299 |
| 101 | 20 | | PA | | 10-0 | 25-53-27 | D02338 | | | | 1 | | | | GD00382 | A.. | 2 | 050-099, 150-199 |
| 102 | 20 | | PA | | 35-0 | 25-53-27 | D02338 | | | | 2 | | | | D05252P | | 21 | 050-099, 150-199 |
| 103 | 20 | | PA | | 35-0 | 25-53-27 | D02338 | | | | 3 | | | | D05252P | | 22 | 050-099, 150-199 |
| 104 | 20 | | PA | | 10-0 | 25-53-27 | D02338 | | | | 12 | | | | GD00382 | S.. | 2 | 050-099, 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0700
Page 22
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0708 | 286T0708 | | | AFT CARGO GUIDE ACTUATORS AND DOOR STOPS (continued) | | | | | | | | | | | |
| 105 | 20 | | PA | 35-0 | 25-53-27 | D02338 | | 14 | | | D05252P | | 23 | | 050-099, 150-199 |
| 111 | 20 | | PA | 11-0 | 25-53-27 | D02340 | | 1 | | | GD00386 | A.. | 2 | | 050-099 |
| 111 | 20 | | PA | 11-0 | 25-53-27 | D02340 | | 1 | | | GD00388 | A.. | 2 | | 150-199 |
| 112 | 20 | | PA | 39-0 | 25-53-27 | D02340 | | 2 | | | D05252P | | 24 | | 050-099 |
| 112 | 20 | | PA | 38-0 | 25-53-27 | D02340 | | 2 | | | D05252P | | 24 | | 150-199 |
| 113 | 20 | | PA | 39-0 | 25-53-27 | D02340 | | 3 | | | D05252P | | 25 | | 050-099 |
| 113 | 20 | | PA | 38-0 | 25-53-27 | D02340 | | 3 | | | D05252P | | 25 | | 150-199 |
| 114 | 20 | | PA | 11-0 | 25-53-27 | D02340 | | 12 | | | GD00388 | S.. | 2 | | 050-099, 150-199 |
| 115 | 20 | | PA | 39-0 | 25-53-27 | D02340 | | 14 | | | D05252P | | 26 | | 050-099 |
| 115 | 20 | | PA | 38-0 | 25-53-27 | D02340 | | 14 | | | D05252P | | 26 | | 150-199 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) | | | | | | | | | | | |
| 011 | 20 | | PA | | 24-0 | 25-53-24 | D01468 | | | | D05258P | | | | 050-099 |
| 011 | 20 | | PA | | 35-0 | 25-53-24 | D01468 | | | | D05258P | | | | 150-199, 275-299 |
| 012 | 20 | | PA | | 24-0 | 25-53-24 | D01468 | | | | D05258P | | | | 050-099 |
| 012 | 20 | | PA | | 35-0 | 25-53-24 | D01468 | | | | D05258P | | | | 150-199, 275-299 |
| 013 | 20 | | PA | | 13-0 | 25-53-24 | D01468 | | | | GD00306 | D.. | 2 | | 050-099 |
| 013 | 20 | | PA | | 12-0 | 25-53-24 | D01468 | | | | GD00306 | D.. | 2 | | 150-199, 275-299 |
| 015 | 18 | | PA | | 13-0 | 25-53-22 | D01468 | | | | GD00306 | A.. | 2 | | 050-099 |
| 015 | 18 | | PA | | 12-0 | 25-53-22 | D01468 | | | | GD00306 | A.. | 2 | | 150-199, 275-299 |
| 016 | 20 | | PA | | 13-0 | 25-53-24 | D01468 | | | | GD00306 | A.. | 2 | | 050-099 |
| 016 | 20 | | PA | | 12-0 | 25-53-24 | D01468 | | | | GD00306 | A.. | 2 | | 150-199, 275-299 |
| 018 | 20 | | PA | | 13-0 | 25-53-22 | D01468 | | | | GD00306 | S.. | 2 | | 050-099 |
| 018 | 20 | | PA | | 12-0 | 25-53-22 | D01468 | | | | GD00306 | S.. | 2 | | 150-199, 275-299 |
| 019 | 20 | | PA | | 13-0 | 25-53-22 | D01468 | | | | GD00306 | S.. | 2 | | 050-099 |
| 019 | 20 | | PA | | 12-0 | 25-53-22 | D01468 | | | | GD00306 | S.. | 2 | | 150-199, 275-299 |
| 021 | 20 | | PA | | 21-0 | 25-53-24 | D01472 | | | | D05258P | | 7 | | 050-099 |
| 021 | 20 | | PA | | 32-0 | 25-53-24 | D01472 | | | | D05258P | | 7 | | 150-199, 275-299 |
| 022 | 20 | | PA | | 21-0 | 25-53-24 | D01472 | | | | D05258P | | 8 | | 050-099 |
| 022 | 20 | | PA | | 32-0 | 25-53-24 | D01472 | | | | D05258P | | 8 | | 150-199, 275-299 |
| 023 | 20 | | PA | | 12-0 | 25-53-24 | D01472 | | | | GD00318 | D.. | 2 | | 050-099 |
| 023 | 20 | | PA | | 11-0 | 25-53-24 | D01472 | | | | GD00318 | D.. | 2 | | 150-199, 275-299 |
| 025 | 18 | | PA | | 12-0 | 25-53-22 | D01472 | | | | GD00318 | A.. | 2 | | 050-099 |
| 025 | 18 | | PA | | 11-0 | 25-53-22 | D01474 | | | | GD00318 | A.. | 2 | | 150-199, 275-299 |
| 026 | 20 | | PA | | 12-0 | 25-53-24 | D01472 | | | | GD00318 | A.. | 2 | | 050-099 |
| 026 | 20 | | PA | | 11-0 | 25-53-24 | D01472 | | | | GD00318 | A.. | 2 | | 150-199, 275-299 |
| 028 | 20 | | PA | | 12-0 | 25-53-22 | D01472 | | | | GD00318 | S.. | 2 | | 050-099 |
| 028 | 20 | | PA | | 11-0 | 25-53-22 | D01474 | | | | GD00318 | S.. | 2 | | 150-199, 275-299 |
| 029 | 20 | | PA | | 12-0 | 25-53-22 | D01472 | | | | GD00318 | S.. | 2 | | 050-099 |
| 029 | 20 | | PA | | 11-0 | 25-53-22 | D01474 | | | | GD00318 | S.. | 2 | | 150-199, 275-299 |
| 031 | 20 | | PA | | 8-0 | 25-53-24 | D01476 | | | | SM00031 | | 9 | | 050-099 |
| 031 | 20 | | PA | | 17-0 | 25-53-24 | D01476 | | | | SM00031 | | 9 | | 150-199, 275-299 |
| 032 | 20 | | PA | | 8-0 | 25-53-24 | D01476 | | | | SM00032 | | 9 | | 050-099 |
| 032 | 20 | | PA | | 17-0 | 25-53-24 | D01476 | | | | SM00032 | | 9 | | 150-199, 275-299 |
| 033 | 20 | | PA | | 12-0 | 25-53-24 | D01476 | | | | GD00330 | D.. | 2 | | 050-099 |
| 033 | 20 | | PA | | 10-0 | 25-53-24 | D01476 | | | | GD04766 | D.. | 2 | | 150-199, 275-299 |
| 035 | 18 | | PA | | 12-0 | 25-53-22 | D01476 | | | | GD00330 | A.. | 2 | | 050-099 |
| 035 | 18 | | PA | | 13-0 | 25-53-22 | D11102 | | | | GD00386 | A.. | 2 | | 150-199, 275-299 |
| 036 | 20 | | PA | | 12-0 | 25-53-24 | D01476 | | | | GD00330 | A.. | 2 | | 050-099 |
| 036 | 20 | | PA | | 10-0 | 25-53-24 | D01476 | | | | GD04766 | A.. | 2 | | 150-199, 275-299 |
| 038 | 20 | | PA | | 12-0 | 25-53-22 | D01476 | | | | GD00330 | S.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | |
| 038 | 20 | | PA | 13-0 | 25-53-22 | D11102 | | 8 | | | | | GD00386 | S.. | 2 | 150-199, 275-299 |
| 039 | 20 | | PA | 12-0 | 25-53-22 | D01476 | | 9 | | | | | GD00330 | S.. | 2 | 050-099 |
| 039 | 20 | | PA | 13-0 | 25-53-22 | D11102 | | 9 | | | | | GD00386 | S.. | 2 | 150-199, 275-299 |
| 041 | 20 | | PA | 20-0 | 25-53-24 | D01480 | | 1 | | | | | SM00031 | | 9 | 050-099 |
| 041 | 20 | | PA | 16-0 | 25-53-24 | D01480 | | 1 | | | | | SM00031 | | 9 | 150-199, 275-299 |
| 042 | 20 | | PA | 20-0 | 25-53-24 | D01480 | | 2 | | | | | SM00032 | | 9 | 050-099 |
| 042 | 20 | | PA | 16-0 | 25-53-24 | D01480 | | 2 | | | | | SM00032 | | 9 | 150-199, 275-299 |
| 043 | 20 | | PA | 7-0 | 25-53-24 | D01480 | | 3 | | | | | GD00342 | D.. | 2 | 050-099 |
| 043 | 20 | | PA | 12-0 | 25-53-24 | D01480 | | 3 | | | | | GD04768 | D.. | 2 | 150-199, 275-299 |
| 045 | 18 | | PA | 7-0 | 25-53-22 | D01480 | | 5 | DK | | | | GD00342 | A.. | 2 | 050-099 |
| 045 | 18 | | PA | 7-0 | 25-53-22 | D01492 | | 5 | DK | | | | GD00330 | A.. | 2 | 150-199, 275-299 |
| 046 | 20 | | PA | 7-0 | 25-53-24 | D01480 | | 6 | | | | | GD00342 | A.. | 2 | 050-099 |
| 046 | 20 | | PA | 12-0 | 25-53-24 | D01480 | | 6 | | | | | GD04768 | A.. | 2 | 150-199, 275-299 |
| 048 | 20 | | PA | 7-0 | 25-53-22 | D01480 | | 8 | | | | | GD00342 | S.. | 2 | 050-099 |
| 048 | 20 | | PA | 7-0 | 25-53-22 | D01492 | | 8 | | | | | GD00330 | S.. | 2 | 150-199, 275-299 |
| 049 | 20 | | PA | 7-0 | 25-53-22 | D01480 | | 9 | | | | | GD00342 | S.. | 2 | 050-099 |
| 049 | 20 | | PA | 7-0 | 25-53-22 | D01492 | | 9 | | | | | GD00330 | S.. | 2 | 150-199, 275-299 |
| 051 | 20 | | PA | 9-0 | 25-53-24 | D01484 | | 1 | | | | | SM00051 | | 9 | 050-099 |
| 051 | 20 | | PA | 10-0 | 25-53-24 | D01498 | | 1 | | | | | SM00051 | | 9 | 150-199, 275-299 |
| 052 | 20 | | PA | 9-0 | 25-53-24 | D01484 | | 2 | | | | | SM00052 | | 9 | 050-099 |
| 052 | 20 | | PA | 10-0 | 25-53-24 | D01498 | | 2 | | | | | SM00052 | | 9 | 150-199, 275-299 |
| 053 | 20 | | PA | 6-0 | 25-53-24 | D01484 | | 3 | | | | | GD00354 | D.. | 2 | 050-099 |
| 053 | 20 | | PA | 6-0 | 25-53-24 | D01498 | | 3 | | | | | GD00354 | D.. | 2 | 150-199, 275-299 |
| 055 | 18 | | PA | 6-0 | 25-53-22 | D01484 | | 5 | DK | | | | GD00354 | A.. | 2 | 050-099 |
| 055 | 18 | | PA | 10-0 | 25-53-22 | D01476 | | 5 | DK | | | | GD04766 | A.. | 2 | 150-199, 275-299 |
| 056 | 20 | | PA | 9-0 | 25-53-24 | D01484 | | 6 | | | | | SM00056 | | 9 | 050-099 |
| 056 | 20 | | PA | 10-0 | 25-53-24 | D01498 | | 6 | | | | | SM00056 | | 9 | 150-199, 275-299 |
| 058 | 20 | | PA | 6-0 | 25-53-22 | D01484 | | 8 | | | | | GD00354 | S.. | 2 | 050-099 |
| 058 | 20 | | PA | 10-0 | 25-53-22 | D01476 | | 8 | | | | | GD04766 | S.. | 2 | 150-199, 275-299 |
| 059 | 20 | | PA | 6-0 | 25-53-22 | D01484 | | 9 | | | | | GD00354 | S.. | 2 | 050-099 |
| 059 | 20 | | PA | 10-0 | 25-53-22 | D01476 | | 9 | | | | | GD04766 | S.. | 2 | 150-199, 275-299 |
| 061 | 20 | | PA | 15-0 | 25-53-24 | D01488 | | 1 | | | | | SM00061 | | 9 | 050-099 |
| 061 | 20 | | PA | 15-0 | 25-53-24 | D01502 | | 1 | | | | | SM00061 | | 9 | 150-199, 275-299 |
| 062 | 20 | | PA | 37-0 | 25-53-24 | D01488 | | 2 | | | | | D05258P | | 30 | 050-099 |
| 062 | 20 | | PA | 35-0 | 25-53-24 | D01502 | | 2 | | | | | D05258P | | 30 | 150-199, 275-299 |
| 063 | 20 | | PA | 17-0 | 25-53-24 | D01488 | | 3 | | | | | GD00354 | D.. | 2 | 050-099 |
| 063 | 20 | | PA | 7-0 | 25-53-24 | D01502 | | 3 | | | | | GD00388 | D.. | 2 | 150-199, 275-299 |
| 065 | 18 | | PA | 17-0 | 25-53-22 | D01488 | | 5 | DK | | | | GD00354 | A.. | 2 | 050-099 |
| 065 | 18 | | PA | 10-0 | 25-53-22 | D01484 | | 5 | DK | | | | GD04770 | A.. | 2 | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|--|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | | | | |
| 066 | 20 | | PA | 14-0 | 25-53-24 | D01488 | | 6 | | | | | | SM00066 | | 9 | | | 050-099 |
| 066 | 20 | | PA | 15-0 | 25-53-24 | D01502 | | 6 | | | | | | SM00066 | | 9 | | | 150-199, 275-299 |
| 068 | 20 | | PA | 17-0 | 25-53-22 | D01488 | | 8 | | | | | | GD00354 | S.. | 2 | | | 050-099 |
| 068 | 20 | | PA | 10-0 | 25-53-22 | D01484 | | 8 | | | | | | GD04770 | S.. | 2 | | | 150-199, 275-299 |
| 069 | 20 | | PA | 17-0 | 25-53-22 | D01488 | | 9 | | | | | | GD00354 | S.. | 2 | | | 050-099 |
| 069 | 20 | | PA | 10-0 | 25-53-22 | D01484 | | 9 | | | | | | GD04770 | S.. | 2 | | | 150-199, 275-299 |
| 071 | 20 | | PA | 15-0 | 25-53-24 | D01494 | | 1 | | | | | | SM00052 | | 9 | | | 050-099 |
| 071 | 20 | | PA | 15-0 | 25-53-24 | D11100 | | 1 | | | | | | SM00052 | | 9 | | | 150-199, 275-299 |
| 072 | 20 | | PA | 15-0 | 25-53-24 | D01494 | | 2 | | | | | | SM00051 | | 9 | | | 050-099 |
| 072 | 20 | | PA | 15-0 | 25-53-24 | D11100 | | 2 | | | | | | SM00051 | | 9 | | | 150-199, 275-299 |
| 073 | 20 | | PA | 7-0 | 25-53-24 | D01494 | | 3 | | | | | | GD00388 | D.. | 2 | | | 050-099 |
| 073 | 20 | | PA | 7-0 | 25-53-24 | D11100 | | 3 | | | | | | GD00386 | D.. | 2 | | | 150-199, 275-299 |
| 075 | 18 | | PA | 8-0 | 25-53-22 | D01494 | | 5 | DK | | | | | GD00386 | A.. | 2 | | | 050-099 |
| 075 | 18 | | PA | 7-0 | 25-53-22 | D01494 | | 5 | DK | | | | | GD00342 | A.. | 2 | | | 150-199, 275-299 |
| 076 | 20 | | PA | 15-0 | 25-53-24 | D01494 | | 6 | | | | | | SM00056 | | 9 | | | 050-099 |
| 076 | 20 | | PA | 15-0 | 25-53-24 | D11100 | | 6 | | | | | | SM00056 | | 9 | | | 150-199, 275-299 |
| 078 | 20 | | PA | 7-0 | 25-53-22 | D01494 | | 8 | | | | | | GD00388 | S.. | 2 | | | 050-099 |
| 078 | 20 | | PA | 8-0 | 25-53-22 | D01494 | | 8 | | | | | | GD00342 | S.. | 2 | | | 150-199, 275-299 |
| 079 | 20 | | PA | 7-0 | 25-53-22 | D01494 | | 9 | | | | | | GD00388 | S.. | 2 | | | 050-099 |
| 079 | 20 | | PA | 8-0 | 25-53-22 | D01494 | | 9 | | | | | | GD00342 | S.. | 2 | | | 150-199, 275-299 |
| 081 | 20 | | PA | 14-0 | 25-53-24 | D01498 | | 1 | | | | | | SM00081 | | 9 | | | 050-099 |
| 081 | 20 | | PA | 13-0 | 25-53-24 | D11106 | | 1 | | | | | | SM00081 | | 9 | | | 150-199, 275-299 |
| 082 | 20 | | PA | 14-0 | 25-53-24 | D01498 | | 2 | | | | | | SM00082 | | 9 | | | 050-099 |
| 082 | 20 | | PA | 13-0 | 25-53-24 | D11106 | | 2 | | | | | | SM00082 | | 9 | | | 150-199, 275-299 |
| 083 | 20 | | PA | 8-0 | 25-53-24 | D01498 | | 3 | | | | | | GD00406 | D.. | 2 | | | 050-099 |
| 083 | 20 | | PA | 8-0 | 25-53-24 | D11106 | | 3 | | | | | | GD00406 | D.. | 2 | | | 150-199, 275-299 |
| 085 | 18 | | PA | 8-0 | 25-53-22 | D01498 | | 5 | DK | | | | | GD00406 | A.. | 2 | | | 050-099 |
| 085 | 18 | | PA | 10-0 | 25-53-22 | D11112 | | 5 | DK | | | | | GD00408 | A.. | 2 | | | 150-199, 275-299 |
| 086 | 20 | | PA | 8-0 | 25-53-24 | D01498 | | 6 | | | | | | GD00406 | A.. | 2 | | | 050-099 |
| 086 | 20 | | PA | 8-0 | 25-53-24 | D11106 | | 6 | | | | | | GD00406 | A.. | 2 | | | 150-199, 275-299 |
| 088 | 20 | | PA | 8-0 | 25-53-22 | D01498 | | 8 | | | | | | GD00406 | S.. | 2 | | | 050-099 |
| 088 | 20 | | PA | 10-0 | 25-53-22 | D11112 | | 8 | | | | | | GD00408 | S.. | 2 | | | 150-199, 275-299 |
| 089 | 20 | | PA | 8-0 | 25-53-22 | D01498 | | 9 | | | | | | GD00406 | S.. | 2 | | | 050-099 |
| 089 | 20 | | PA | 10-0 | 25-53-22 | D11112 | | 9 | | | | | | GD00408 | S.. | 2 | | | 150-199, 275-299 |
| 091 | 20 | | PA | 13-0 | 25-53-24 | D01502 | | 1 | | | | | | SM00081 | | 9 | | | 050-099 |
| 091 | 20 | | PA | 13-0 | 25-53-24 | D11110 | | 1 | | | | | | SM00081 | | 9 | | | 150-199, 275-299 |
| 092 | 20 | | PA | 13-0 | 25-53-24 | D01502 | | 2 | | | | | | SM00082 | | 9 | | | 050-099 |
| 092 | 20 | | PA | 13-0 | 25-53-24 | D11110 | | 2 | | | | | | SM00082 | | 9 | | | 150-199, 275-299 |
| 093 | 20 | | PA | 5-0 | 25-53-24 | D01502 | | 3 | | | | | | GD00408 | D.. | 2 | | | 050-099 |

WIRE LIST

D280T132

91-21-11
Section W0710
Page 3
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | |
| 093 | 20 | | PA | 5-0 | 25-53-24 | D11110 | | 3 | | | | | GD00408 | D.. | 2 | 150-199, 275-299 |
| 095 | 18 | | PA | 5-0 | 25-53-22 | D01502 | | 5 | DK | | | | GD00408 | A.. | 2 | 050-099 |
| 095 | 18 | | PA | 7-0 | 25-53-22 | D01502 | | 5 | DK | | | | GD00388 | A.. | 2 | 150-199, 275-299 |
| 096 | 20 | | PA | 5-0 | 25-53-24 | D01502 | | 6 | | | | | GD00408 | A.. | 2 | 050-099 |
| 096 | 20 | | PA | 5-0 | 25-53-24 | D11110 | | 6 | | | | | GD00408 | A.. | 2 | 150-199, 275-299 |
| 098 | 20 | | PA | 5-0 | 25-53-22 | D01502 | | 8 | | | | | GD00408 | S.. | 2 | 050-099 |
| 098 | 20 | | PA | 7-0 | 25-53-22 | D01502 | | 8 | | | | | GD00388 | S.. | 2 | 150-199, 275-299 |
| 099 | 20 | | PA | 5-0 | 25-53-22 | D01502 | | 9 | | | | | GD00408 | S.. | 2 | 050-099 |
| 099 | 20 | | PA | 7-0 | 25-53-22 | D01502 | | 9 | | | | | GD00388 | S.. | 2 | 150-199, 275-299 |
| 101 | 18 | | PA | 5-0 | 25-53-22 | D01482 | | 5 | DK | | | | GD04768 | A.. | 2 | 150-199, 275-299 |
| 102 | 20 | | PA | 5-0 | 25-53-22 | D01482 | | 8 | | | | | GD04768 | S.. | 2 | 150-199, 275-299 |
| 104 | 20 | | PA | 5-0 | 25-53-22 | D01482 | | 9 | | | | | GD04768 | S.. | 2 | 150-199, 275-299 |
| 105 | 18 | | PA | 12-0 | 25-53-22 | D11108 | | 5 | DK | | | | GD00406 | A.. | 2 | 150-199, 275-299 |
| 106 | 20 | | PA | 12-0 | 25-53-22 | D11108 | | 8 | | | | | GD00406 | S.. | 2 | 150-199, 275-299 |
| 107 | 20 | | PA | 12-0 | 25-53-22 | D11108 | | 9 | | | | | GD00406 | S.. | 2 | 150-199, 275-299 |
| 108 | 18 | | PA | 11-0 | 25-53-22 | D01500 | | 5 | DK | | | | GD00354 | A.. | 2 | 150-199, 275-299 |
| 109 | 20 | | PA | 11-0 | 25-53-22 | D01500 | | 8 | | | | | GD00354 | S.. | 2 | 150-199, 275-299 |
| 110 | 20 | | PA | 11-0 | 25-53-22 | D01500 | | 9 | | | | | GD00354 | S.. | 2 | 150-199, 275-299 |
| 111 | 20 | | PA | 20-0 | 25-53-24 | D01470 | | 1 | | | | | D05258P | 4 | | 050-099 |
| 111 | 20 | | PA | 30-0 | 25-53-24 | D01470 | | 1 | | | | | D05258P | 4 | | 150-199, 275-299 |
| 112 | 20 | | PA | 20-0 | 25-53-24 | D01470 | | 2 | | | | | D05258P | 5 | | 050-099 |
| 112 | 20 | | PA | 30-0 | 25-53-24 | D01470 | | 2 | | | | | D05258P | 5 | | 150-199, 275-299 |
| 113 | 20 | | PA | 8-0 | 25-53-24 | D01470 | | 3 | | | | | GD00306 | D.. | 2 | 050-099 |
| 113 | 20 | | PA | 7-0 | 25-53-24 | D01470 | | 3 | | | | | GD00306 | D.. | 2 | 150-199, 275-299 |
| 114 | 18 | | PA | 8-0 | 25-53-22 | D11106 | | 5 | DK | | | | GD00406 | A.. | 2 | 150-199, 275-299 |
| 115 | 18 | | PA | 8-0 | 25-53-22 | D01470 | | 5 | DK | | | | GD00306 | A.. | 2 | 050-099 |
| 115 | 18 | | PA | 7-0 | 25-53-22 | D01470 | | 5 | DK | | | | GD00306 | A.. | 2 | 150-199, 275-299 |
| 116 | 20 | | PA | 8-0 | 25-53-24 | D01470 | | 6 | | | | | GD00306 | A.. | 2 | 050-099 |
| 116 | 20 | | PA | 7-0 | 25-53-24 | D01470 | | 6 | | | | | GD00306 | A.. | 2 | 150-199, 275-299 |
| 118 | 20 | | PA | 8-0 | 25-53-22 | D01470 | | 8 | | | | | GD00306 | S.. | 2 | 050-099 |
| 118 | 20 | | PA | 7-0 | 25-53-22 | D01470 | | 8 | | | | | GD00306 | S.. | 2 | 150-199, 275-299 |
| 119 | 20 | | PA | 8-0 | 25-53-22 | D01470 | | 9 | | | | | GD00306 | S.. | 2 | 050-099 |
| 119 | 20 | | PA | 7-0 | 25-53-22 | D01470 | | 9 | | | | | GD00306 | S.. | 2 | 150-199, 275-299 |
| 120 | 20 | | PA | 8-0 | 25-53-22 | D11106 | | 8 | | | | | GD00406 | S.. | 2 | 150-199, 275-299 |
| 121 | 20 | | PA | 16-0 | 25-53-24 | D01474 | | 1 | | | | | D05258P | 11 | | 050-099 |
| 121 | 20 | | PA | 27-0 | 25-53-24 | D01474 | | 1 | | | | | D05258P | 11 | | 150-199, 275-299 |
| 122 | 20 | | PA | 16-0 | 25-53-24 | D01474 | | 2 | | | | | D05258P | 12 | | 050-099 |
| 122 | 20 | | PA | 27-0 | 25-53-24 | D01474 | | 2 | | | | | D05258P | 12 | | 150-199, 275-299 |
| 123 | 20 | | PA | 8-0 | 25-53-24 | D01474 | | 3 | | | | | GD00318 | D.. | 2 | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | |
| 123 | 20 | | PA | 6-0 | 25-53-24 | D01474 | | 3 | | | GD00318 | D.. | 2 | | 150-199, 275-299 |
| 124 | 20 | | PA | 8-0 | 25-53-22 | D11106 | | 9 | | | GD00406 | S.. | 2 | | 150-199, 275-299 |
| 125 | 18 | | PA | 8-0 | 25-53-22 | D01474 | | 5 | DK | | GD00318 | A.. | 2 | | 050-099 |
| 125 | 18 | | PA | 11-0 | 25-53-22 | D01472 | | 5 | DK | | GD00318 | A.. | 2 | | 150-199, 275-299 |
| 126 | 20 | | PA | 8-0 | 25-53-24 | D01474 | | 6 | | | GD00318 | A.. | 2 | | 050-099 |
| 126 | 20 | | PA | 6-0 | 25-53-24 | D01474 | | 6 | | | GD00318 | A.. | 2 | | 150-199, 275-299 |
| 127 | 18 | | PA | 12-0 | 25-53-22 | D01480 | | 5 | DK | | GD04768 | A.. | 2 | | 150-199, 275-299 |
| 128 | 20 | | PA | 8-0 | 25-53-22 | D01474 | | 8 | | | GD00318 | S.. | 2 | | 050-099 |
| 128 | 20 | | PA | 11-0 | 25-53-22 | D01472 | | 8 | | | GD00318 | S.. | 2 | | 150-199, 275-299 |
| 129 | 20 | | PA | 8-0 | 25-53-22 | D01474 | | 9 | | | GD00318 | S.. | 2 | | 050-099 |
| 129 | 20 | | PA | 11-0 | 25-53-22 | D01472 | | 9 | | | GD00318 | S.. | 2 | | 150-199, 275-299 |
| 130 | 20 | | PA | 12-0 | 25-53-22 | D01480 | | 8 | | | GD04768 | S.. | 2 | | 150-199, 275-299 |
| 131 | 20 | | PA | 5-0 | 25-53-24 | D01478 | | 1 | | | SM00041 | | 9 | | 050-099 |
| 131 | 20 | | PA | 12-0 | 25-53-24 | D01478 | | 1 | | | SM00041 | | 9 | | 150-199, 275-299 |
| 132 | 20 | | PA | 5-0 | 25-53-24 | D01478 | | 2 | | | SM00042 | | 9 | | 050-099 |
| 132 | 20 | | PA | 12-0 | 25-53-24 | D01478 | | 2 | | | SM00042 | | 9 | | 150-199, 275-299 |
| 133 | 20 | | PA | 7-0 | 25-53-24 | D01478 | | 3 | | | GD00330 | D.. | 2 | | 050-099 |
| 133 | 20 | | PA | 5-0 | 25-53-24 | D01478 | | 3 | | | GD04766 | D.. | 2 | | 150-199, 275-299 |
| 134 | 20 | | PA | 12-0 | 25-53-22 | D01480 | | 9 | | | GD04768 | S.. | 2 | | 150-199, 275-299 |
| 135 | 18 | | PA | 7-0 | 25-53-22 | D01478 | | 5 | DK | | GD00330 | A.. | 2 | | 050-099 |
| 135 | 18 | | PA | 5-0 | 25-53-22 | D01478 | | 5 | DK | | GD04766 | A.. | 2 | | 150-199, 275-299 |
| 136 | 20 | | PA | 7-0 | 25-53-24 | D01478 | | 6 | | | GD00330 | A.. | 2 | | 050-099 |
| 136 | 20 | | PA | 5-0 | 25-53-24 | D01478 | | 6 | | | GD04766 | A.. | 2 | | 150-199, 275-299 |
| 137 | 18 | | PA | 6-0 | 25-53-22 | D01498 | | 5 | DK | | GD00354 | A.. | 2 | | 150-199, 275-299 |
| 138 | 20 | | PA | 7-0 | 25-53-22 | D01478 | | 8 | | | GD00330 | S.. | 2 | | 050-099 |
| 138 | 20 | | PA | 5-0 | 25-53-22 | D01478 | | 8 | | | GD04766 | S.. | 2 | | 150-199, 275-299 |
| 139 | 20 | | PA | 7-0 | 25-53-22 | D01478 | | 9 | | | GD00330 | S.. | 2 | | 050-099 |
| 139 | 20 | | PA | 5-0 | 25-53-22 | D01478 | | 9 | | | GD04766 | S.. | 2 | | 150-199, 275-299 |
| 140 | 20 | | PA | 6-0 | 25-53-22 | D01498 | | 8 | | | GD00354 | S.. | 2 | | 150-199, 275-299 |
| 141 | 20 | | PA | 25-0 | 25-53-24 | D01482 | | 1 | | | SM00041 | | 9 | | 050-099 |
| 141 | 20 | | PA | 11-0 | 25-53-24 | D01482 | | 1 | | | SM00041 | | 9 | | 150-199, 275-299 |
| 142 | 20 | | PA | 25-0 | 25-53-24 | D01482 | | 2 | | | SM00042 | | 9 | | 050-099 |
| 142 | 20 | | PA | 11-0 | 25-53-24 | D01482 | | 2 | | | SM00042 | | 9 | | 150-199, 275-299 |
| 143 | 20 | | PA | 12-0 | 25-53-24 | D01482 | | 3 | | | GD00342 | D.. | 2 | | 050-099 |
| 143 | 20 | | PA | 5-0 | 25-53-24 | D01482 | | 3 | | | GD04768 | D.. | 2 | | 150-199, 275-299 |
| 144 | 20 | | PA | 6-0 | 25-53-22 | D01498 | | 9 | | | GD00354 | S.. | 2 | | 150-199, 275-299 |
| 145 | 18 | | PA | 12-0 | 25-53-22 | D01482 | | 5 | DK | | GD00342 | A.. | 2 | | 050-099 |
| 145 | 18 | | PA | 12-0 | 25-53-22 | D01488 | | 5 | DK | | GD00330 | A.. | 2 | | 150-199, 275-299 |
| 146 | 20 | | PA | 12-0 | 25-53-24 | D01482 | | 6 | | | GD00342 | A.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 5

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | | |
| 146 | 20 | | PA | 5-0 | 25-53-24 | D01482 | | 6 | | | | | GD04768 | A.. | 2 | | 150-199, 275-299 |
| 147 | 20 | | PA | 6-0 | 25-53-24 | D05258P | | 3 | | | | | SM00001 | | 9 | | 150-199, 275-299 |
| 148 | 20 | | PA | 12-0 | 25-53-22 | D01482 | | 8 | | | | | GD00342 | S.. | 2 | | 050-099 |
| 148 | 20 | | PA | 12-0 | 25-53-22 | D01488 | | 8 | | | | | GD00330 | S.. | 2 | | 150-199, 275-299 |
| 149 | 20 | | PA | 12-0 | 25-53-22 | D01482 | | 9 | | | | | GD00342 | S.. | 2 | | 050-099 |
| 149 | 20 | | PA | 12-0 | 25-53-22 | D01488 | | 9 | | | | | GD00330 | S.. | 2 | | 150-199, 275-299 |
| 150 | 20 | | PA | 6-0 | 25-53-24 | D05258P | | 6 | | | | | SM00002 | | 9 | | 150-199, 275-299 |
| 151 | 20 | | PA | 16-0 | 25-53-24 | D01486 | | 1 | | | | | SM00071 | | 9 | | 050-099 |
| 151 | 20 | | PA | 17-0 | 25-53-24 | D01500 | | 1 | | | | | SM00071 | | 9 | | 150-199, 275-299 |
| 152 | 20 | | PA | 16-0 | 25-53-24 | D01486 | | 2 | | | | | SM00072 | | 9 | | 050-099 |
| 152 | 20 | | PA | 17-0 | 25-53-24 | D01500 | | 2 | | | | | SM00072 | | 9 | | 150-199, 275-299 |
| 153 | 20 | | PA | 10-0 | 25-53-24 | D01486 | | 3 | | | | | GD00354 | D.. | 2 | | 050-099 |
| 153 | 20 | | PA | 11-0 | 25-53-24 | D01500 | | 3 | | | | | GD00354 | D.. | 2 | | 150-199, 275-299 |
| 154 | 20 | | PA | 8-0 | 25-53-24 | D01492 | | 1 | | | | | SM00001 | | 9 | | 150-199, 275-299 |
| 155 | 18 | | PA | 10-0 | 25-53-22 | D01486 | | 5 | DK | | | | GD00354 | A.. | 2 | | 050-099 |
| 155 | 18 | | PA | 12-0 | 25-53-22 | D01496 | | 5 | DK | | | | GD00342 | A.. | 2 | | 150-199, 275-299 |
| 156 | 20 | | PA | 16-0 | 25-53-24 | D01486 | | 6 | | | | | SM00076 | | 9 | | 050-099 |
| 156 | 20 | | PA | 17-0 | 25-53-24 | D01500 | | 6 | | | | | SM00076 | | 9 | | 150-199, 275-299 |
| 157 | 20 | | PA | 8-0 | 25-53-24 | D01492 | | 2 | | | | | SM00002 | | 9 | | 150-199, 275-299 |
| 158 | 20 | | PA | 10-0 | 25-53-22 | D01486 | | 8 | | | | | GD00354 | S.. | 2 | | 050-099 |
| 158 | 20 | | PA | 12-0 | 25-53-22 | D01496 | | 8 | | | | | GD00342 | S.. | 2 | | 150-199, 275-299 |
| 159 | 20 | | PA | 10-0 | 25-53-22 | D01486 | | 9 | | | | | GD00354 | S.. | 2 | | 050-099 |
| 159 | 20 | | PA | 12-0 | 25-53-22 | D01496 | | 9 | | | | | GD00342 | S.. | 2 | | 150-199, 275-299 |
| 160 | 20 | | PA | 8-0 | 25-53-24 | D01492 | | 6 | | | | | GD00330 | A.. | 2 | | 150-199, 275-299 |
| 161 | 20 | | PA | 17-0 | 25-53-24 | D01492 | | 1 | | | | | SM00061 | | 9 | | 050-099 |
| 161 | 20 | | PA | 17-0 | 25-53-24 | D01504 | | 1 | | | | | SM00061 | | 9 | | 150-199, 275-299 |
| 162 | 20 | | PA | 17-0 | 25-53-24 | D01492 | | 2 | | | | | SM00062 | | 9 | | 050-099 |
| 162 | 20 | | PA | 17-0 | 25-53-24 | D01504 | | 2 | | | | | SM00062 | | 9 | | 150-199, 275-299 |
| 163 | 20 | | PA | 22-0 | 25-53-24 | D01492 | | 3 | | | | | GD00386 | D.. | 2 | | 050-099 |
| 163 | 20 | | PA | 14-0 | 25-53-24 | D01504 | | 3 | | | | | GD00354 | D.. | 2 | | 150-199, 275-299 |
| 164 | 20 | | PA | 8-0 | 25-53-24 | D01492 | | 3 | | | | | GD00330 | D.. | 2 | | 150-199, 275-299 |
| 165 | 18 | | PA | 22-0 | 25-53-22 | D01492 | | 5 | DK | | | | GD00386 | A.. | 2 | | 050-099 |
| 165 | 18 | | PA | 6-0 | 25-53-22 | D01486 | | 5 | DK | | | | GD04770 | A.. | 2 | | 150-199, 275-299 |
| 166 | 20 | | PA | 16-0 | 25-53-24 | D01492 | | 6 | | | | | SM00066 | | 9 | | 050-099 |
| 166 | 20 | | PA | 17-0 | 25-53-24 | D01504 | | 6 | | | | | SM00066 | | 9 | | 150-199, 275-299 |
| 167 | 20 | | PA | 28-0 | 25-53-24 | D01496 | | 1 | | | | | SM00001 | | 9 | | 150-199, 275-299 |
| 168 | 20 | | PA | 22-0 | 25-53-22 | D01492 | | 8 | | | | | GD00386 | S.. | 2 | | 050-099 |
| 168 | 20 | | PA | 5-0 | 25-53-22 | D01486 | | 8 | | | | | GD04770 | S.. | 2 | | 150-199, 275-299 |
| 169 | 20 | | PA | 22-0 | 25-53-22 | D01492 | | 9 | | | | | GD00386 | S.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | |
| 169 | 20 | PA | | 5-0 | 25-53-22 | D01486 | | 9 | | | GD04770 | S.. | 2 | | 150-199, 275-299 |
| 170 | 20 | PA | | 28-0 | 25-53-24 | D01496 | | 2 | | | SM00002 | | 9 | | 150-199, 275-299 |
| 171 | 20 | PA | | 20-0 | 25-53-24 | D01496 | | 1 | | | SM00072 | | 9 | | 050-099 |
| 171 | 20 | PA | | 20-0 | 25-53-24 | D11102 | | 1 | | | SM00072 | | 9 | | 150-199, 275-299 |
| 172 | 20 | PA | | 20-0 | 25-53-24 | D01496 | | 2 | | | SM00071 | | 9 | | 050-099 |
| 172 | 20 | PA | | 20-0 | 25-53-24 | D11102 | | 2 | | | SM00071 | | 9 | | 150-199, 275-299 |
| 173 | 20 | PA | | 12-0 | 25-53-24 | D01496 | | 3 | | | GD00386 | D.. | 2 | | 050-099 |
| 173 | 20 | PA | | 13-0 | 25-53-24 | D11102 | | 3 | | | GD00386 | D.. | 2 | | 150-199, 275-299 |
| 174 | 20 | PA | | 12-0 | 25-53-24 | D01496 | | 6 | | | GD00342 | A.. | 2 | | 150-199, 275-299 |
| 175 | 18 | PA | | 12-0 | 25-53-22 | D01496 | | 5 | DK | | GD00386 | A.. | 2 | | 050-099 |
| 175 | 18 | PA | | 13-0 | 25-53-22 | D11104 | | 5 | DK | | GD00354 | A.. | 2 | | 150-199, 275-299 |
| 176 | 20 | PA | | 20-0 | 25-53-24 | D01496 | | 6 | | | SM00076 | | 9 | | 050-099 |
| 176 | 20 | PA | | 20-0 | 25-53-24 | D11102 | | 6 | | | SM00076 | | 9 | | 150-199, 275-299 |
| 177 | 20 | PA | | 12-0 | 25-53-24 | D01496 | | 3 | | | GD00342 | D.. | 2 | | 150-199, 275-299 |
| 178 | 20 | PA | | 11-0 | 25-53-22 | D01496 | | 8 | | | GD00388 | S.. | 2 | | 050-099 |
| 178 | 20 | PA | | 13-0 | 25-53-22 | D11104 | | 8 | | | GD00354 | S.. | 2 | | 150-199, 275-299 |
| 179 | 20 | PA | | 11-0 | 25-53-22 | D01496 | | 9 | | | GD00388 | S.. | 2 | | 050-099 |
| 179 | 20 | PA | | 13-0 | 25-53-22 | D11104 | | 9 | | | GD00354 | S.. | 2 | | 150-199, 275-299 |
| 180 | 20 | PA | | 10-0 | 25-53-24 | D05258P | | 9 | | | SM00003 | | 9 | | 150-199, 275-299 |
| 181 | 20 | PA | | 18-0 | 25-53-24 | D01500 | | 1 | | | SM00091 | | 9 | | 050-099 |
| 181 | 20 | PA | | 17-0 | 25-53-24 | D11108 | | 1 | | | SM00091 | | 9 | | 150-199, 275-299 |
| 182 | 20 | PA | | 18-0 | 25-53-24 | D01500 | | 2 | | | SM00092 | | 9 | | 050-099 |
| 182 | 20 | PA | | 17-0 | 25-53-24 | D11108 | | 2 | | | SM00092 | | 9 | | 150-199, 275-299 |
| 183 | 20 | PA | | 11-0 | 25-53-24 | D01500 | | 3 | | | GD00406 | D.. | 2 | | 050-099 |
| 183 | 20 | PA | | 12-0 | 25-53-24 | D11108 | | 3 | | | GD00406 | D.. | 2 | | 150-199, 275-299 |
| 184 | 20 | PA | | 10-0 | 25-53-24 | D05258P | | 13 | | | SM00004 | | 9 | | 150-199, 275-299 |
| 185 | 18 | PA | | 11-0 | 25-53-22 | D01500 | | 5 | DK | | GD00406 | A.. | 2 | | 050-099 |
| 185 | 18 | PA | | 5-0 | 25-53-22 | D11110 | | 5 | DK | | GD00408 | A.. | 2 | | 150-199, 275-299 |
| 186 | 20 | PA | | 11-0 | 25-53-24 | D01500 | | 6 | | | GD00406 | A.. | 2 | | 050-099 |
| 186 | 20 | PA | | 12-0 | 25-53-24 | D11108 | | 6 | | | GD00406 | A.. | 2 | | 150-199, 275-299 |
| 187 | 20 | PA | | 8-0 | 25-53-24 | D01488 | | 1 | | | SM00003 | | 9 | | 150-199, 275-299 |
| 188 | 20 | PA | | 11-0 | 25-53-22 | D01500 | | 8 | | | GD00406 | S.. | 2 | | 050-099 |
| 188 | 20 | PA | | 5-0 | 25-53-22 | D11110 | | 8 | | | GD00408 | S.. | 2 | | 150-199, 275-299 |
| 189 | 20 | PA | | 11-0 | 25-53-22 | D01500 | | 9 | | | GD00406 | S.. | 2 | | 050-099 |
| 189 | 20 | PA | | 5-0 | 25-53-22 | D11110 | | 9 | | | GD00408 | S.. | 2 | | 150-199, 275-299 |
| 190 | 20 | PA | | 8-0 | 25-53-24 | D01488 | | 2 | | | SM00004 | | 9 | | 150-199, 275-299 |
| 191 | 20 | PA | | 18-0 | 25-53-24 | D01504 | | 1 | | | SM00091 | | 9 | | 050-099 |
| 191 | 20 | PA | | 18-0 | 25-53-24 | D11112 | | 1 | | | SM00091 | | 9 | | 150-199, 275-299 |
| 192 | 20 | PA | | 18-0 | 25-53-24 | D01504 | | 2 | | | SM00092 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 7

Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | |
| 192 | 20 | | PA | 18-0 | 25-53-24 | D11112 | | 2 | | | | | | | 150-199, 275-299 |
| 193 | 20 | | PA | 10-0 | 25-53-24 | D01504 | | 3 | | | | D.. | 2 | | 050-099 |
| 193 | 20 | | PA | 10-0 | 25-53-24 | D11112 | | 3 | | | | D.. | 2 | | 150-199, 275-299 |
| 194 | 20 | | PA | 12-0 | 25-53-24 | D01488 | | 6 | | | | A.. | 2 | | 150-199, 275-299 |
| 195 | 18 | | PA | 10-0 | 25-53-22 | D01504 | | 5 | DK | | | A.. | 2 | | 050-099 |
| 195 | 18 | | PA | 8-0 | 25-53-22 | D11100 | | 5 | DK | | | A.. | 2 | | 150-199, 275-299 |
| 196 | 20 | | PA | 10-0 | 25-53-24 | D01504 | | 6 | | | | A.. | 2 | | 050-099 |
| 196 | 20 | | PA | 10-0 | 25-53-24 | D11112 | | 6 | | | | A.. | 2 | | 150-199, 275-299 |
| 197 | 20 | | PA | 12-0 | 25-53-24 | D01488 | | 3 | | | | D.. | 2 | | 150-199, 275-299 |
| 198 | 20 | | PA | 10-0 | 25-53-22 | D01504 | | 8 | | | | S.. | 2 | | 050-099 |
| 198 | 20 | | PA | 8-0 | 25-53-22 | D11100 | | 8 | | | | S.. | 2 | | 150-199, 275-299 |
| 199 | 20 | | PA | 10-0 | 25-53-22 | D01504 | | 9 | | | | S.. | 2 | | 050-099 |
| 199 | 20 | | PA | 8-0 | 25-53-22 | D11100 | | 9 | | | | S.. | 2 | | 150-199, 275-299 |
| 301B | 20 | | PC AA | 7-0 | 25-53-22 | D05254P | | 1 | | | | | 9 | | 050-099 |
| 301B | 20 | | PC AA | 6-0 | 25-53-22 | D05254P | | 1 | | | | | 9 | | 150-199, 275-299 |
| 301R | 20 | | PC AA | 0-0 | 25-53-22 | D05254P | | 2 | | | | | 9 | | ALL |
| 301Y | 20 | | PC AA | 0-0 | 25-53-22 | D05254P | | 3 | | | | | 9 | | ALL |
| 302B | 20 | | PC AB | 7-0 | 25-53-22 | D05254P | | 4 | | | | | 9 | | 050-099 |
| 302B | 20 | | PC AB | 24-0 | 25-53-22 | D05254P | | 4 | | | | | 9 | | 150-199, 275-299 |
| 302R | 20 | | PC AB | 0-0 | 25-53-22 | D05254P | | 5 | | | | | 9 | | 050-099 |
| 302R | 20 | | PC AB | 0-0 | 25-53-22 | D05254P | | 5 | | | | | 9 | | 150-199, 275-299 |
| 302Y | 20 | | PC AB | 0-0 | 25-53-22 | D05254P | | 6 | | | | | 9 | | 050-099 |
| 302Y | 20 | | PC AB | 0-0 | 25-53-22 | D05254P | | 6 | | | | | 9 | | 150-199, 275-299 |
| 303B | 20 | | PC AC | 22-0 | 25-53-22 | D05254P | | 7 | | | | | 9 | | 050-099 |
| 303B | 20 | | PC AC | 8-0 | 25-53-22 | D01492 | | 4 | | | | | 9 | | 150-199, 275-299 |
| 303R | 20 | | PC AC | 0-0 | 25-53-22 | D05254P | | 8 | | | | | 9 | | 050-099 |
| 303R | 20 | | PC AC | 0-0 | 25-53-22 | D01492 | | 7 | | | | | 9 | | 150-199, 275-299 |
| 303Y | 20 | | PC AC | 0-0 | 25-53-22 | D05254P | | 9 | | | | | 9 | | 050-099 |
| 303Y | 20 | | PC AC | 0-0 | 25-53-22 | D01492 | | 10 | | | | | 9 | | 150-199, 275-299 |
| 304B | 20 | | PC AD | 27-0 | 25-53-22 | D05254P | | 11 | | | | | 9 | | ALL |
| 304R | 20 | | PC AD | 0-0 | 25-53-22 | D05254P | | 12 | | | | | 9 | | ALL |
| 304Y | 20 | | PC AD | 0-0 | 25-53-22 | D05254P | | 13 | | | | | 9 | | ALL |
| 305B | 20 | | PC AE | 20-0 | 25-53-22 | D05256P | | 1 | | | | | 9 | | 050-099 |
| 305B | 20 | | PC AE | 8-0 | 25-53-22 | D05256P | | 1 | | | | | 9 | | 150-199, 275-299 |
| 305R | 20 | | PC AE | 0-0 | 25-53-22 | D05256P | | 2 | | | | | 9 | | ALL |
| 305Y | 20 | | PC AE | 0-0 | 25-53-22 | D05256P | | 3 | | | | | 9 | | ALL |
| 306B | 20 | | PC AF | 20-0 | 25-53-22 | D05256P | | 4 | | | | | 9 | | 050-099 |
| 306B | 20 | | PC AF | 6-0 | 25-53-22 | D05256P | | 4 | | | | | 9 | | 150-199, 275-299 |
| 306R | 20 | | PC AF | 0-0 | 25-53-22 | D05256P | | 5 | | | | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | |
| 306R | 20 | PC | AF | | 0-0 | 25-53-22 | D05256P | | 5 | | | SM00015 | | 9 | 150-199, 275-299 |
| 306Y | 20 | PC | AF | | 0-0 | 25-53-22 | D05256P | | 6 | | | SM00120 | | 9 | 050-099 |
| 306Y | 20 | PC | AF | | 0-0 | 25-53-22 | D05256P | | 6 | | | SM00016 | | 9 | 150-199, 275-299 |
| 307B | 20 | PC | AG | | 19-0 | 25-53-22 | D05256P | | 7 | | | SM00134 | | 9 | ALL |
| 307R | 20 | PC | AG | | 0-0 | 25-53-22 | D05256P | | 8 | | | SM00137 | | 9 | ALL |
| 307Y | 20 | PC | AG | | 0-0 | 25-53-22 | D05256P | | 9 | | | SM00130 | | 9 | ALL |
| 308B | 20 | PC | AH | | 19-0 | 25-53-22 | D05256P | | 11 | | | SM00144 | | 9 | 050-099 |
| 308B | 20 | PC | AH | | 39-0 | 25-53-22 | D11102 | | 4 | | | SM00114 | | 9 | 150-199, 275-299 |
| 308R | 20 | PC | AH | | 0-0 | 25-53-22 | D05256P | | 12 | | | SM00147 | | 9 | 050-099 |
| 308R | 20 | PC | AH | | 0-0 | 25-53-22 | D11102 | | 7 | | | SM00117 | | 9 | 150-199, 275-299 |
| 308Y | 20 | PC | AH | | 0-0 | 25-53-22 | D05256P | | 13 | | | SM00140 | | 9 | 050-099 |
| 308Y | 20 | PC | AH | | 0-0 | 25-53-22 | D11102 | | 10 | | | SM00110 | | 9 | 150-199, 275-299 |
| 310B | 20 | PC | AI | | 5-0 | 25-53-22 | SM00024 | | | 9 | | SM00034 | | 9 | 150-199, 275-299 |
| 310R | 20 | PC | AI | | 0-0 | 25-53-22 | SM00027 | | | 9 | | SM00037 | | 9 | 150-199, 275-299 |
| 310Y | 20 | PC | AI | | 0-0 | 25-53-22 | SM00020 | | | 9 | | SM00030 | | 9 | 150-199, 275-299 |
| 311B | 20 | PC | BA | | 21-0 | 25-53-22 | D01468 | | 4 | | | SM00014 | | 9 | 050-099 |
| 311B | 20 | PC | BA | | 32-0 | 25-53-22 | D01468 | | 4 | | | SM00014 | | 9 | 150-199, 275-299 |
| 311R | 20 | PC | BA | | 0-0 | 25-53-22 | D01468 | | 7 | | | SM00017 | | 9 | ALL |
| 311Y | 20 | PC | BA | | 0-0 | 25-53-22 | D01468 | | 10 | | | SM00010 | | 9 | ALL |
| 312B | 20 | PC | BB | | 18-0 | 25-53-22 | D01472 | | 4 | | | SM00024 | | 9 | 050-099 |
| 312B | 20 | PC | BB | | 24-0 | 25-53-22 | D01474 | | 4 | | | SM00005 | | 9 | 150-199, 275-299 |
| 312R | 20 | PC | BB | | 0-0 | 25-53-22 | D01472 | | 7 | | | SM00027 | | 9 | 050-099 |
| 312R | 20 | PC | BB | | 0-0 | 25-53-22 | D01474 | | 7 | | | SM00006 | | 9 | 150-199, 275-299 |
| 312Y | 20 | PC | BB | | 0-0 | 25-53-22 | D01472 | | 10 | | | SM00020 | | 9 | 050-099 |
| 312Y | 20 | PC | BB | | 0-0 | 25-53-22 | D01474 | | 10 | | | SM00007 | | 9 | 150-199, 275-299 |
| 313B | 20 | PC | BC | | 12-0 | 25-53-22 | D01476 | | 4 | | | SM00034 | | 9 | 050-099 |
| 313B | 20 | PC | BC | | 25-0 | 25-53-22 | D11108 | | 4 | | | SM00144 | | 9 | 150-199, 275-299 |
| 313R | 20 | PC | BC | | 0-0 | 25-53-22 | D01476 | | 7 | | | SM00037 | | 9 | 050-099 |
| 313R | 20 | PC | BC | | 0-0 | 25-53-22 | D11108 | | 7 | | | SM00147 | | 9 | 150-199, 275-299 |
| 313Y | 20 | PC | BC | | 0-0 | 25-53-22 | D01476 | | 10 | | | SM00030 | | 9 | 050-099 |
| 313Y | 20 | PC | BC | | 0-0 | 25-53-22 | D11108 | | 10 | | | SM00140 | | 9 | 150-199, 275-299 |
| 314B | 20 | PC | BD | | 24-0 | 25-53-22 | D01480 | | 4 | | | SM00024 | | 9 | 050-099 |
| 314B | 20 | PC | BD | | 16-0 | 25-53-22 | D11104 | | 4 | | | SM00009 | | 9 | 150-199, 275-299 |
| 314R | 20 | PC | BD | | 0-0 | 25-53-22 | D01480 | | 7 | | | SM00027 | | 9 | 050-099 |
| 314R | 20 | PC | BD | | 0-0 | 25-53-22 | D11104 | | 7 | | | SM00011 | | 9 | 150-199, 275-299 |
| 314Y | 20 | PC | BD | | 0-0 | 25-53-22 | D01480 | | 10 | | | SM00020 | | 9 | 050-099 |
| 314Y | 20 | PC | BD | | 0-0 | 25-53-22 | D11104 | | 10 | | | SM00012 | | 9 | 150-199, 275-299 |
| 315B | 20 | PC | BE | | 11-0 | 25-53-22 | D01484 | | 4 | | | SM00034 | | 9 | 050-099 |
| 315B | 20 | PC | BE | | 45-0 | 25-53-22 | D01476 | | 4 | | | SM00044 | | 9 | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 9

Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | |
| 315R | 20 | PC | BE | 0-0 | 25-53-22 | D01484 | | 7 | | | | | SM00037 | 9 | | 050-099 |
| 315R | 20 | PC | BE | 0-0 | 25-53-22 | D01476 | | 7 | | | | | SM00047 | 9 | | 150-199, 275-299 |
| 315Y | 20 | PC | BE | 0-0 | 25-53-22 | D01484 | | 10 | | | | | SM00030 | 9 | | 050-099 |
| 315Y | 20 | PC | BE | 0-0 | 25-53-22 | D01476 | | 10 | | | | | SM00040 | 9 | | 150-199, 275-299 |
| 316B | 20 | PC | BF | 32-0 | 25-53-22 | D01488 | | 4 | | | | | SM00014 | 9 | | 050-099 |
| 316B | 20 | PC | BF | 16-0 | 25-53-22 | D01484 | | 4 | | | | | SM00014 | 9 | | 150-199, 275-299 |
| 316R | 20 | PC | BF | 0-0 | 25-53-22 | D01488 | | 7 | | | | | SM00017 | 9 | | 050-099 |
| 316R | 20 | PC | BF | 0-0 | 25-53-22 | D01484 | | 7 | | | | | SM00017 | 9 | | 150-199, 275-299 |
| 316Y | 20 | PC | BF | 0-0 | 25-53-22 | D01488 | | 10 | | | | | SM00010 | 9 | | 050-099 |
| 316Y | 20 | PC | BF | 0-0 | 25-53-22 | D01484 | | 10 | | | | | SM00010 | 9 | | 150-199, 275-299 |
| 317B | 20 | PC | BG | 11-0 | 25-53-22 | D01494 | | 4 | | | | | SM00044 | 9 | | 050-099 |
| 317B | 20 | PC | BG | 15-0 | 25-53-22 | D01494 | | 4 | | | | | SM00044 | 9 | | 150-199, 275-299 |
| 317R | 20 | PC | BG | 0-0 | 25-53-22 | D01494 | | 7 | | | | | SM00047 | 9 | | ALL |
| 317Y | 20 | PC | BG | 0-0 | 25-53-22 | D01494 | | 10 | | | | | SM00040 | 9 | | ALL |
| 318B | 20 | PC | BH | 35-0 | 25-53-22 | D01498 | | 4 | | | | | SM00024 | 9 | | 050-099 |
| 318B | 20 | PC | BH | 21-0 | 25-53-22 | D11112 | | 4 | | | | | SM00009 | 9 | | 150-199, 275-299 |
| 318R | 20 | PC | BH | 0-0 | 25-53-22 | D01498 | | 7 | | | | | SM00027 | 9 | | 050-099 |
| 318R | 20 | PC | BH | 0-0 | 25-53-22 | D11112 | | 7 | | | | | SM00011 | 9 | | 150-199, 275-299 |
| 318Y | 20 | PC | BH | 0-0 | 25-53-22 | D01498 | | 10 | | | | | SM00020 | 9 | | 050-099 |
| 318Y | 20 | PC | BH | 0-0 | 25-53-22 | D11112 | | 10 | | | | | SM00012 | 9 | | 150-199, 275-299 |
| 319B | 20 | PC | BJ | 13-0 | 25-53-22 | D01502 | | 4 | | | | | SM00044 | 9 | | 050-099 |
| 319B | 20 | PC | BJ | 10-0 | 25-53-22 | D01502 | | 4 | | | | | SM00044 | 9 | | 150-199, 275-299 |
| 319R | 20 | PC | BJ | 0-0 | 25-53-22 | D01502 | | 7 | | | | | SM00047 | 9 | | ALL |
| 319Y | 20 | PC | BJ | 0-0 | 25-53-22 | D01502 | | 10 | | | | | SM00040 | 9 | | ALL |
| 320B | 20 | PC | AJ | 18-0 | 25-53-22 | D11106 | | 4 | | | | | SM00034 | 9 | | 150-199, 275-299 |
| 320R | 20 | PC | AJ | 0-0 | 25-53-22 | D11106 | | 7 | | | | | SM00037 | 9 | | 150-199, 275-299 |
| 320Y | 20 | PC | AJ | 0-0 | 25-53-22 | D11106 | | 10 | | | | | SM00030 | 9 | | 150-199, 275-299 |
| 321B | 20 | PC | CA | 30-0 | 25-53-22 | D01470 | | 4 | | | | | SM00114 | 9 | | 050-099 |
| 321B | 20 | PC | CA | 24-0 | 25-53-22 | D01470 | | 4 | | | | | SM00114 | 9 | | 150-199, 275-299 |
| 321R | 20 | PC | CA | 0-0 | 25-53-22 | D01470 | | 7 | | | | | SM00117 | 9 | | ALL |
| 321Y | 20 | PC | CA | 0-0 | 25-53-22 | D01470 | | 10 | | | | | SM00110 | 9 | | ALL |
| 322B | 20 | PC | CB | 27-0 | 25-53-22 | D01474 | | 4 | | | | | SM00124 | 9 | | 050-099 |
| 322B | 20 | PC | CB | 29-0 | 25-53-22 | D01472 | | 4 | | | | | SM00013 | 9 | | 150-199, 275-299 |
| 322R | 20 | PC | CB | 0-0 | 25-53-22 | D01474 | | 7 | | | | | SM00127 | 9 | | 050-099 |
| 322R | 20 | PC | CB | 0-0 | 25-53-22 | D01472 | | 7 | | | | | SM00015 | 9 | | 150-199, 275-299 |
| 322Y | 20 | PC | CB | 0-0 | 25-53-22 | D01474 | | 10 | | | | | SM00120 | 9 | | 050-099 |
| 322Y | 20 | PC | CB | 0-0 | 25-53-22 | D01472 | | 10 | | | | | SM00016 | 9 | | 150-199, 275-299 |
| 323B | 20 | PC | CC | 13-0 | 25-53-22 | D01478 | | 4 | | | | | SM00134 | 9 | | 050-099 |
| 323B | 20 | PC | CC | 30-0 | 25-53-22 | D01478 | | 4 | | | | | SM00134 | 9 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | |
| 323R | 20 | PC | CC | 0-0 | 25-53-22 | D01478 | | 7 | | | SM00137 | | 9 | | ALL |
| 323Y | 20 | PC | CC | 0-0 | 25-53-22 | D01478 | | 10 | | | SM00130 | | 9 | | ALL |
| 324B | 20 | PC | CD | 15-0 | 25-53-22 | D01482 | | 4 | | | SM00124 | | 9 | | 050-099 |
| 324B | 20 | PC | CD | 13-0 | 25-53-22 | D01488 | | 4 | | | SM00013 | | 9 | | 150-199, 275-299 |
| 324R | 20 | PC | CD | 0-0 | 25-53-22 | D01482 | | 7 | | | SM00127 | | 9 | | 050-099 |
| 324R | 20 | PC | CD | 0-0 | 25-53-22 | D01488 | | 7 | | | SM00015 | | 9 | | 150-199, 275-299 |
| 324Y | 20 | PC | CD | 0-0 | 25-53-22 | D01482 | | 10 | | | SM00120 | | 9 | | 050-099 |
| 324Y | 20 | PC | CD | 0-0 | 25-53-22 | D01488 | | 10 | | | SM00016 | | 9 | | 150-199, 275-299 |
| 325B | 20 | PC | CE | 19-0 | 25-53-22 | D01486 | | 4 | | | SM00134 | | 9 | | 050-099 |
| 325B | 20 | PC | CE | 16-0 | 25-53-22 | D01496 | | 4 | | | SM00134 | | 9 | | 150-199, 275-299 |
| 325R | 20 | PC | CE | 0-0 | 25-53-22 | D01486 | | 7 | | | SM00137 | | 9 | | 050-099 |
| 325R | 20 | PC | CE | 0-0 | 25-53-22 | D01496 | | 7 | | | SM00137 | | 9 | | 150-199, 275-299 |
| 325Y | 20 | PC | CE | 0-0 | 25-53-22 | D01486 | | 10 | | | SM00130 | | 9 | | 050-099 |
| 325Y | 20 | PC | CE | 0-0 | 25-53-22 | D01496 | | 10 | | | SM00130 | | 9 | | 150-199, 275-299 |
| 326B | 20 | PC | CF | 21-0 | 25-53-22 | D01492 | | 4 | | | SM00114 | | 9 | | 050-099 |
| 326B | 20 | PC | CF | 8-0 | 25-53-22 | D01486 | | 4 | | | SM00114 | | 9 | | 150-199, 275-299 |
| 326R | 20 | PC | CF | 0-0 | 25-53-22 | D01492 | | 7 | | | SM00117 | | 9 | | 050-099 |
| 326R | 20 | PC | CF | 0-0 | 25-53-22 | D01486 | | 7 | | | SM00117 | | 9 | | 150-199, 275-299 |
| 326Y | 20 | PC | CF | 0-0 | 25-53-22 | D01492 | | 10 | | | SM00110 | | 9 | | 050-099 |
| 326Y | 20 | PC | CF | 0-0 | 25-53-22 | D01486 | | 10 | | | SM00110 | | 9 | | 150-199, 275-299 |
| 327B | 20 | PC | CG | 23-0 | 25-53-22 | D01496 | | 4 | | | SM00144 | | 9 | | 050-099 |
| 327B | 20 | PC | CG | 31-0 | 25-53-22 | D11100 | | 4 | | | SM00014 | | 9 | | 150-199, 275-299 |
| 327R | 20 | PC | CG | 0-0 | 25-53-22 | D01496 | | 7 | | | SM00147 | | 9 | | 050-099 |
| 327R | 20 | PC | CG | 0-0 | 25-53-22 | D11100 | | 7 | | | SM00017 | | 9 | | 150-199, 275-299 |
| 327Y | 20 | PC | CG | 0-0 | 25-53-22 | D01496 | | 10 | | | SM00140 | | 9 | | 050-099 |
| 327Y | 20 | PC | CG | 0-0 | 25-53-22 | D11100 | | 10 | | | SM00010 | | 9 | | 150-199, 275-299 |
| 328B | 20 | PC | CH | 25-0 | 25-53-22 | D01500 | | 4 | | | SM00124 | | 9 | | 050-099 |
| 328B | 20 | PC | CH | 34-0 | 25-53-22 | D11110 | | 4 | | | SM00013 | | 9 | | 150-199, 275-299 |
| 328R | 20 | PC | CH | 0-0 | 25-53-22 | D01500 | | 7 | | | SM00127 | | 9 | | 050-099 |
| 328R | 20 | PC | CH | 0-0 | 25-53-22 | D11110 | | 7 | | | SM00015 | | 9 | | 150-199, 275-299 |
| 328Y | 20 | PC | CH | 0-0 | 25-53-22 | D01500 | | 10 | | | SM00120 | | 9 | | 050-099 |
| 328Y | 20 | PC | CH | 0-0 | 25-53-22 | D11110 | | 10 | | | SM00016 | | 9 | | 150-199, 275-299 |
| 329B | 20 | PC | CJ | 26-0 | 25-53-22 | D01504 | | 4 | | | SM00144 | | 9 | | 050-099 |
| 329B | 20 | PC | CJ | 20-0 | 25-53-22 | SM00009 | | | 9 | | SM00005 | | 9 | | 150-199, 275-299 |
| 329R | 20 | PC | CJ | 0-0 | 25-53-22 | D01504 | | 7 | | | SM00147 | | 9 | | 050-099 |
| 329R | 20 | PC | CJ | 0-0 | 25-53-22 | SM00011 | | | 9 | | SM00006 | | 9 | | 150-199, 275-299 |
| 329Y | 20 | PC | CJ | 0-0 | 25-53-22 | D01504 | | 10 | | | SM00140 | | 9 | | 050-099 |
| 329Y | 20 | PC | CJ | 0-0 | 25-53-22 | SM00012 | | | 9 | | SM00007 | | 9 | | 150-199, 275-299 |
| 330B | 20 | PC | AN | 19-0 | 25-53-22 | D01500 | | 4 | | | SM00144 | | 9 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | | |
| 330R | 20 | PC | AN | 0-0 | 25-53-22 | D01500 | | 7 | | | | | SM00147 | | 9 | | 150-199, 275-299 |
| 330Y | 20 | PC | AN | 0-0 | 25-53-22 | D01500 | | 10 | | | | | SM00140 | | 9 | | 150-199, 275-299 |
| 331B | 20 | PC | AR | 36-0 | 25-53-22 | D01480 | | 4 | | | | | SM00034 | | 9 | | 150-199, 275-299 |
| 331R | 20 | PC | AR | 0-0 | 25-53-22 | D01480 | | 7 | | | | | SM00037 | | 9 | | 150-199, 275-299 |
| 331Y | 20 | PC | AR | 0-0 | 25-53-22 | D01480 | | 10 | | | | | SM00030 | | 9 | | 150-199, 275-299 |
| 332B | 20 | PC | AQ | 14-0 | 25-53-22 | D01498 | | 4 | | | | | SM00024 | | 9 | | 150-199, 275-299 |
| 332R | 20 | PC | AQ | 0-0 | 25-53-22 | D01498 | | 7 | | | | | SM00027 | | 9 | | 150-199, 275-299 |
| 332Y | 20 | PC | AQ | 0-0 | 25-53-22 | D01498 | | 10 | | | | | SM00020 | | 9 | | 150-199, 275-299 |
| 333B | 20 | PC | AK | 10-0 | 25-53-22 | D05256P | | 11 | | | | | SM00124 | | 9 | | 150-199, 275-299 |
| 333R | 20 | PC | AK | 0-0 | 25-53-22 | D05256P | | 12 | | | | | SM00127 | | 9 | | 150-199, 275-299 |
| 333Y | 20 | PC | AK | 0-0 | 25-53-22 | D05256P | | 13 | | | | | SM00120 | | 9 | | 150-199, 275-299 |
| 334B | 20 | PC | AL | 20-0 | 25-53-22 | D01482 | | 4 | | | | | SM00124 | | 9 | | 150-199, 275-299 |
| 334R | 20 | PC | AL | 0-0 | 25-53-22 | D01482 | | 7 | | | | | SM00127 | | 9 | | 150-199, 275-299 |
| 334Y | 20 | PC | AL | 0-0 | 25-53-22 | D01482 | | 10 | | | | | SM00120 | | 9 | | 150-199, 275-299 |
| 335B | 20 | PC | AM | 11-0 | 25-53-22 | SM00124 | | | | 9 | | | SM00144 | | 9 | | 150-199, 275-299 |
| 335R | 20 | PC | AM | 0-0 | 25-53-22 | SM00127 | | | | 9 | | | SM00147 | | 9 | | 150-199, 275-299 |
| 335Y | 20 | PC | AM | 0-0 | 25-53-22 | SM00120 | | | | 9 | | | SM00140 | | 9 | | 150-199, 275-299 |
| 336B | 20 | PC | DF | 21-0 | 25-53-22 | D01490 | | 4 | | | | | SM00134 | | 9 | | 050-099 |
| 336B | 20 | PC | DF | 22-0 | 25-53-22 | D01504 | | 4 | | | | | SM00134 | | 9 | | 150-199, 275-299 |
| 336R | 20 | PC | DF | 0-0 | 25-53-22 | D01490 | | 7 | | | | | SM00137 | | 9 | | 050-099 |
| 336R | 20 | PC | DF | 0-0 | 25-53-22 | D01504 | | 7 | | | | | SM00137 | | 9 | | 150-199, 275-299 |
| 336Y | 20 | PC | DF | 0-0 | 25-53-22 | D01490 | | 10 | | | | | SM00130 | | 9 | | 050-099 |
| 336Y | 20 | PC | DF | 0-0 | 25-53-22 | D01504 | | 10 | | | | | SM00130 | | 9 | | 150-199, 275-299 |
| 338B | 20 | PC | AP | 19-0 | 25-53-22 | D05254P | | 7 | | | | | SM00024 | | 9 | | 150-199, 275-299 |
| 338R | 20 | PC | AP | 0-0 | 25-53-22 | D05254P | | 8 | | | | | SM00027 | | 9 | | 150-199, 275-299 |
| 338Y | 20 | PC | AP | 0-0 | 25-53-22 | D05254P | | 9 | | | | | SM00020 | | 9 | | 150-199, 275-299 |
| 501 | 20 | PA | | 20-0 | 25-53-24 | D01494 | | 1 | | | | | SM00003 | | 9 | | 150-199, 275-299 |
| 502 | 20 | PA | | 20-0 | 25-53-24 | D01494 | | 2 | | | | | SM00004 | | 9 | | 150-199, 275-299 |
| 503 | 20 | PA | | 8-0 | 25-53-24 | D01494 | | 6 | | | | | GD00342 | A.. | 2 | | 150-199, 275-299 |
| 504 | 20 | PA | | 8-0 | 25-53-24 | D01494 | | 3 | | | | | GD00342 | D.. | 2 | | 150-199, 275-299 |
| 507 | 20 | PA | | 19-0 | 25-53-24 | D05258P | | 16 | | | | | D01484 | | 1 | | 150-199, 275-299 |
| 508 | 20 | PA | | 19-0 | 25-53-24 | D05258P | | 19 | | | | | D01484 | | 2 | | 150-199, 275-299 |
| 509 | 20 | PA | | 10-0 | 25-53-24 | D01484 | | 6 | | | | | GD04770 | A.. | 2 | | 150-199, 275-299 |
| 510 | 20 | PA | | 10-0 | 25-53-24 | D01484 | | 3 | | | | | GD04770 | D.. | 2 | | 150-199, 275-299 |
| 513 | 20 | PA | | 13-0 | 25-53-24 | D05258P | | 29 | | | | | D01486 | | 1 | | 150-199, 275-299 |
| 514 | 20 | PA | | 13-0 | 25-53-24 | D05258P | | 33 | | | | | D01486 | | 2 | | 150-199, 275-299 |
| 515 | 20 | PA | | 5-0 | 25-53-24 | D01486 | | 6 | | | | | GD04770 | A.. | 2 | | 150-199, 275-299 |
| 516 | 20 | PA | | 5-0 | 25-53-24 | D01486 | | 3 | | | | | GD04770 | D.. | 2 | | 150-199, 275-299 |
| 531 | 20 | PA | | 10-0 | 25-53-24 | D05258P | | 14 | | | | | SM00031 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | |
| 531 | 20 | | PA | 11-0 | 25-53-24 | D05258P | | 14 | | | | | | | | 150-199, 275-299 |
| 532 | 20 | | PA | 10-0 | 25-53-24 | D05258P | | 15 | | | | | | | | 050-099 |
| 532 | 20 | | PA | 11-0 | 25-53-24 | D05258P | | 15 | | | | | | | | 150-199, 275-299 |
| 541 | 20 | | PA | 10-0 | 25-53-24 | D05258P | | 17 | | | | | | | | 050-099 |
| 541 | 20 | | PA | 11-0 | 25-53-24 | D05258P | | 17 | | | | | | | | 150-199, 275-299 |
| 542 | 20 | | PA | 10-0 | 25-53-24 | D05258P | | 18 | | | | | | | | 050-099 |
| 542 | 20 | | PA | 11-0 | 25-53-24 | D05258P | | 18 | | | | | | | | 150-199, 275-299 |
| 551 | 20 | | PA | 25-0 | 25-53-24 | D05258P | | 21 | | | | | | | | 050-099 |
| 551 | 20 | | PA | 24-0 | 25-53-24 | D05258P | | 21 | | | | | | | | 150-199, 275-299 |
| 552 | 20 | | PA | 25-0 | 25-53-24 | D05258P | | 22 | | | | | | | | 050-099 |
| 552 | 20 | | PA | 24-0 | 25-53-24 | D05258P | | 22 | | | | | | | | 150-199, 275-299 |
| 556 | 20 | | PA | 25-0 | 25-53-24 | D05258P | | 23 | | | | | | | | 050-099 |
| 556 | 20 | | PA | 24-0 | 25-53-24 | D05258P | | 23 | | | | | | | | 150-199, 275-299 |
| 561 | 20 | | PA | 25-0 | 25-53-24 | D05258P | | 10 | | | | | | | | 050-099 |
| 561 | 20 | | PA | 24-0 | 25-53-24 | D05258P | | 10 | | | | | | | | 150-199, 275-299 |
| 562 | 20 | | PA | 25-0 | 25-53-24 | D05258P | | 20 | | | | | | | | 050-099 |
| 562 | 20 | | PA | 24-0 | 25-53-24 | D05258P | | 20 | | | | | | | | 150-199, 275-299 |
| 566 | 20 | | PA | 25-0 | 25-53-24 | D05258P | | 40 | | | | | | | | 050-099 |
| 566 | 20 | | PA | 24-0 | 25-53-24 | D05258P | | 40 | | | | | | | | 150-199, 275-299 |
| 571 | 20 | | PA | 22-0 | 25-53-24 | D05258P | | 24 | | | | | | | | 050-099 |
| 571 | 20 | | PA | 23-0 | 25-53-24 | D05258P | | 24 | | | | | | | | 150-199, 275-299 |
| 572 | 20 | | PA | 22-0 | 25-53-24 | D05258P | | 25 | | | | | | | | 050-099 |
| 572 | 20 | | PA | 23-0 | 25-53-24 | D05258P | | 25 | | | | | | | | 150-199, 275-299 |
| 576 | 20 | | PA | 22-0 | 25-53-24 | D05258P | | 26 | | | | | | | | 050-099 |
| 576 | 20 | | PA | 23-0 | 25-53-24 | D05258P | | 26 | | | | | | | | 150-199, 275-299 |
| 581 | 20 | | PA | 27-0 | 25-53-24 | D05258P | | 27 | | | | | | | | ALL |
| 582 | 20 | | PA | 27-0 | 25-53-24 | D05258P | | 28 | | | | | | | | ALL |
| 591 | 20 | | PA | 27-0 | 25-53-24 | D05258P | | 31 | | | | | | | | ALL |
| 592 | 20 | | PA | 27-0 | 25-53-24 | D05258P | | 32 | | | | | | | | ALL |
| 661 | 20 | | PA | 16-0 | 25-53-24 | D01490 | | 1 | | | | | | | | 050-099 |
| 661 | 20 | | PA | 16-0 | 25-53-24 | D11104 | | 1 | | | | | | | | 150-199, 275-299 |
| 662 | 20 | | PA | 16-0 | 25-53-24 | D01490 | | 2 | | | | | | | | 050-099 |
| 662 | 20 | | PA | 16-0 | 25-53-24 | D11104 | | 2 | | | | | | | | 150-199, 275-299 |
| 663 | 20 | | PA | 21-0 | 25-53-24 | D01490 | | 3 | | | | | | | | 050-099 |
| 663 | 20 | | PA | 13-0 | 25-53-24 | D11104 | | 3 | | | | | | | | 150-199, 275-299 |
| 665 | 18 | | PA | 21-0 | 25-53-22 | D01490 | | 5 | DK | | | | | | | 050-099 |
| 665 | 18 | | PA | 13-0 | 25-53-22 | D01504 | | 5 | DK | | | | | | | 150-199, 275-299 |
| 666 | 20 | | PA | 16-0 | 25-53-24 | D01490 | | 6 | | | | | | | | 050-099 |
| 666 | 20 | | PA | 16-0 | 25-53-24 | D11104 | | 6 | | | | | | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|---|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0710 | 286T0710 | | | AFT CARGO POWER DRIVE UNITS (PDU) (continued) | | | | | | | | | | | | | |
| 668 | 20 | | PA | 21-0 | 25-53-22 | D01490 | | 8 | | | | | GD00386 | S.. | 2 | | 050-099 |
| 668 | 20 | | PA | 13-0 | 25-53-22 | D01504 | | 8 | | | | | GD00354 | S.. | 2 | | 150-199, 275-299 |
| 669 | 20 | | PA | 21-0 | 25-53-22 | D01490 | | 9 | | | | | GD00386 | S.. | 2 | | 050-099 |
| 669 | 20 | | PA | 13-0 | 25-53-22 | D01504 | | 9 | | | | | GD00354 | S.. | 2 | | 150-199, 275-299 |
| W0711 | 286T0711 | | | P8 TO E2-3 SHELF (AIDS) | | | | | | | | | | | | | |
| 040 | 24 | | PK | 29-2 | 31-36-11 | D02301 | | R | | | | | D04765J | | 23 | | ALL |
| 041 | 20 | | PA | 3-5 | 31-36-11 | D02301 | | N | | | | | GD04472 | A.. | 2 | | 050-099, 275-299 |
| 041 | 22 | | PA | 3-5 | 31-36-11 | D02301 | | N | | | | | GD04472 | A.. | 2 | | 150-199 |
| 042 | 20 | | PA | 3-5 | 31-36-11 | D02301 | | L | | | | | GD04474 | D.. | 2 | | 050-099, 275-299 |
| 042 | 22 | | PA | 3-5 | 31-36-11 | D02301 | | L | | | | | GD04474 | D.. | 2 | | 150-199 |
| 043 | 20 | | PA | 3-5 | 31-36-11 | D02301 | | G- | | | | | GD04474 | D.. | 2 | | 050-099, 275-299 |
| 043 | 22 | | PA | 3-5 | 31-36-11 | D02301 | | G- | | | | | GD04474 | D.. | 2 | | 150-199 |
| 044 | 20 | | PA | 3-5 | 33-13-18 | D02301 | | M | | | | | GD04474 | A.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 045 | 20 | | PA | 7-7 | 33-13-18 | D02301 | | E- | | | | | SP02270 | | 9 | | 050-099, 150-155, 162-165, 275-276 |
| 056 | 20 | | PA | 3-5 | 23-22-12 | D02301 | | P | | | | | GD04472 | S.. | 2 | * | ALL |
| 211 | 20 | | UA | 1-6 | 31-35-11 | D02301 | | REF | | IK | | | GD04472 | S.. | 2 | | ALL |
| 211B | 24 | | PW | IK | 29-2 | 31-35-11 | D02301 | | D | | | | D04765J | | 27 | | ALL |
| 211R | 24 | | PW | IK | 0-0 | 31-35-11 | D02301 | | C | | | | D04765J | | 28 | | ALL |
| 211Z | 24 | | PW | IK | 0-0 | 31-35-11 | D02301 | | REF | | IK | | D04765J | | 29 | | ALL |
| 213 | 20 | | UA | 1-6 | 31-36-11 | D02301 | | REF | | IM | | | GD04474 | S.. | 2 | | ALL |
| 213B | 24 | | PW | IM | 29-2 | 31-36-11 | D02301 | | F | | | | D04765J | | 25 | | ALL |
| 213R | 24 | | PW | IM | 0-0 | 31-36-11 | D02301 | | E | | | | D04765J | | 24 | | ALL |
| 213Z | 24 | | PW | IM | 0-0 | 31-36-11 | D02301 | | REF | | IM | | D04765J | | 26 | | ALL |
| 214 | 20 | | UA | 1-6 | 23-22-12 | D02301 | | REF | | IN | | | GD04472 | S.. | 2 | * | ALL |
| 214B | 24 | | PW | IN | 11-1 | 23-22-12 | D02301 | | B | | | | TB0255Y | C003 | BJ | | ALL |
| 214R | 24 | | PW | IN | 0-0 | 23-22-12 | D02301 | | A | | | | TB0255Y | A003 | BJ | | ALL |
| 214Z | 24 | | PW | IN | 0-0 | 23-22-12 | D02301 | | REF | | IN | | TB0255Y | A004 | BJ | | ALL |
| 215 | 20 | | UA | 1-6 | 34-61-16 | D02301 | | REF | | IO | | | GD04472 | REF | # | | ALL |
| 215B | 24 | | PW | IO | 11-1 | 34-61-16 | D02301 | | CAP | Y | | | TB0255X | C005 | BJ | | ALL |
| 215R | 24 | | PW | IO | 0-0 | 34-61-16 | D02301 | | CAP | Y | | | TB0255X | B005 | BJ | | ALL |
| 215Z | 24 | | PW | IO | 0-0 | 34-61-16 | D02301 | | REF | | IO | | TB0255X | A005 | BJ | | ALL |
| 216 | 20 | | UA | 1-6 | 34-61-26 | D02301 | | REF | | IP | | | GD04472 | REF | # | | ALL |
| 216B | 24 | | PW | IP | 11-1 | 34-61-26 | D02301 | | CAP | Y | | | TB0255X | B006 | BJ | | ALL |
| 216R | 24 | | PW | IP | 0-0 | 34-61-26 | D02301 | | CAP | Y | | | TB0255X | A006 | BJ | | ALL |
| 216Z | 24 | | PW | IP | 0-0 | 34-61-26 | D02301 | | REF | | IP | | TB0255X | D005 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0711 | 286T0711 | | | P8 TO E2-3 SHELF (AIDS) (continued) | | | | | | | | | | | |
| 221B | 20 | PB | IU | | 7-7 | 33-13-18 | D02301 | | M | | SP04096 | | 9 | | 156-157, 166-199, 277-299 |
| 221R | 20 | PB | IU | | 0-0 | 33-13-18 | D02301 | | E- | | SP02270 | | 9 | | 156-157, 166-199, 277-299 |
| W0712 | 286T0712 | | | OXYGEN DEPLOYMENT FEEDER | | | | | | | | | | | |
| 001 | 24 | PK | | | 22-2 | 35-21-11 | D05708P | | 1 | | D05710P | | 1 | | ALL |
| 002 | 24 | PK | | | 22-2 | 35-21-11 | D05708P | | 2 | | D05710P | | 2 | | ALL |
| 003 | 22 | PA | | | 22-2 | SPARE | D05708P | | 3 | | D05710P | | 3 | | ALL |
| 004 | 22 | PA | | | 22-2 | SPARE | D05708P | | 4 | | D05710P | | 4 | | ALL |
| 005 | 24 | PK | | | 22-2 | 35-21-11 | D05708P | | 5 | | D05710P | | 5 | | ALL |
| 006 | 22 | PA | | | 22-2 | 35-21-11 | D05708P | | 6 | | D05710P | | 6 | | ALL |
| 008 | 24 | PK | | | 4-0 | 35-21-11 | D00964 | | 1 | | D05710P | | 8 | | ALL |
| 009 | 20 | PA | | | 2-0 | 35-21-11 | D00964 | | 2 | | GD01662 | | D.. | 2 | ALL |
| 012 | 12 | PA | | | 22-2 | 35-21-12 | D05708P | | 14 | | D05710P | | 14 | | ALL |
| 016 | 12 | PA | | | 22-2 | 35-21-13 | D05708P | | 16 | | D05710P | | 16 | | ALL |
| 018 | 12 | PA | | | 22-2 | 35-21-14 | D05708P | | 18 | | D05710P | | 18 | | ALL |
| 019 | 22 | PA | | | 22-2 | 33-51-11 | D05708P | | 7 | | D05710P | | 7 | | ALL |
| 020 | 20 | PQ | | A | 22-2 | 33-51-11 | D05708P | | 9 | | D05710P | | 9 | | ALL |
| 020Z | | | | A | 0-0 | 33-51-11 | D05708P | | DED | | D05710P | | DED | | ALL |
| 021 | 20 | PQ | | B | 22-2 | 33-51-11 | D05708P | | 10 | | D05710P | | 10 | | ALL |
| 021Z | | | | B | 0-0 | 33-51-11 | D05708P | | DED | | D05710P | | DED | | ALL |
| 022 | 22 | PA | | | 22-2 | 33-51-11 | D05708P | | 11 | | D05710P | | 11 | | ALL |
| W0713 | 286T0713 | | | E2-3 TO DIGITAL FLIGHT DATA RECORDER | | | | | | | | | | | |
| 001 | 22 | PA | | | 132-0 | 31-31-11 | D00307A | | 23 | | D04741J | | 1 | | 050-099 |
| 001 | 22 | PA | | | 154-0 | 31-31-11 | D00307A | | 23 | | D04741J | | 1 | | 150-199, 275-299 |
| 002 | 22 | PA | | | 132-0 | 31-31-11 | D00307A | | 1 | | D04741J | | 2 | | 050-099 |
| 002 | 22 | PA | | | 154-0 | 31-31-11 | D00307A | | 1 | | D04741J | | 2 | | 150-199, 275-299 |
| 004 | 24 | PK | | | 132-0 | 31-31-11 | D00307A | | 21 | | D04741J | | 4 | | 050-099 |
| 004 | 24 | PK | | | 156-0 | 31-31-11 | D00307A | | 21 | | D04741J | | 4 | | 150-199, 275-299 |
| 005 | 24 | PK | | | 132-0 | 31-31-11 | D00307A | | 22 | | D04741J | | 12 | | 050-099 |
| 005 | 24 | PK | | | 154-0 | 31-31-11 | D00307A | | 22 | | D04741J | | 12 | | 150-199, 275-299 |
| 006 | 20 | PA | | | 5-0 | 31-31-11 | D00307A | | 2 | | GD00173 | | A.. | E | ALL |
| 007 | 20 | PA | | | 3-0 | 31-31-11 | D00307A | | 6 | | GD00741 | | S.. | E | ALL |
| 009 | 22 | PA | | | 132-0 | SPARE | D04741J | | 13 | | D00307A | | CAP | Y | 050-099 |
| 009 | 22 | PA | | | 154-0 | SPARE | D04741J | | 13 | | D00307A | | CAP | Y | 150-199, 275-299 |
| 010 | 22 | PA | | | 132-0 | SPARE | D04741J | | 14 | | D00307A | | CAP | Y | 050-099 |
| 010 | 22 | PA | | | 154-0 | SPARE | D04741J | | 14 | | D00307A | | CAP | Y | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0713 | 286T0713 | | | E2-3 TO DIGITAL FLIGHT DATA RECORDER (continued) | | | | | | | | | | | | |
| 202 | 20 | | UA | 1-6 | 31-31-11 | D00307A | | REF | | IB | GD00741 | S.. | E | | 050-099 | |
| 202 | 20 | | UA | 3-0 | 31-31-11 | D00307A | | | | IB | GD00741 | S.. | E | | 150-199, 275-299 | |
| 202B | 24 | | PW | 132-0 | 31-31-11 | D00307A | | 8 | | | D04741J | 9 | | | 050-099 | |
| 202B | 24 | | PW | 154-0 | 31-31-11 | D00307A | | 8 | | | D04741J | 9 | | | 150-199, 275-299 | |
| 202R | 24 | | PW | 0-0 | 31-31-11 | D00307A | | 7 | | | D04741J | 8 | | | ALL | |
| 202Z | | | IB | 0-0 | 31-31-11 | D00307A | | REF | | IB | D04741J | 5 | | | 050-099 | |
| 202Z | | | IB | 0-0 | 31-31-11 | D04741J | | 5 | | | D00307A | | | IB | 150-199, 275-278 | |
| 202Z | | | IB | 0-0 | 31-31-11 | D00307A | | | | IB | D04741J | 5 | | | 280-299 | |
| 203 | 20 | | UA | 1-6 | 31-31-11 | D00307A | | REF | | IC | GD00741 | S.. | E | | 050-099 | |
| 203 | 20 | | UA | 3-0 | 31-31-11 | D00307A | | | | IC | GD00741 | S.. | E | | 150-199, 275-299 | |
| 203B | 24 | | PW | 132-0 | 31-31-11 | D00307A | | 10 | | | D04741J | 11 | | | 050-099 | |
| 203B | 24 | | PW | 154-0 | 31-31-11 | D00307A | | 10 | | | D04741J | 11 | | | 150-199, 275-299 | |
| 203R | 24 | | PW | 0-0 | 31-31-11 | D00307A | | 9 | | | D04741J | 10 | | | ALL | |
| 203Z | | | IC | 0-0 | 31-31-11 | D00307A | | REF | | IC | D04741J | 21 | | | 050-099 | |
| 203Z | | | IC | 0-0 | 31-31-11 | D00307A | | | | IC | D04741J | 21 | | | 150-199, 275-299 | |
| W0714 | 286T0714 | | | LEFT AND CENTER AND RIGHT FWD OXYGEN DEPLOYMENT | | | | | | | | | | | | |
| 001 | 20 | | PA | 16-0 | 35-21-12 | D05448P | | 1 | | | SM00003 | | S | | 050-099 | |
| 001 | 20 | | PA | 7-0 | 35-21-12 | D05448P | | 1 | | | SM00002 | | S | | 150-199 | |
| 001 | 20 | | PA | 14-0 | 35-21-12 | D05448P | | 1 | | | SM00003 | | S | | 275-299 | |
| 005 | 20 | | PA | 22-0 | 35-21-12 | SP03638 | | | S | | SM00003 | | S | | 050-099 | |
| 005 | 20 | | PA | 15-0 | 35-21-12 | SM00003 | | | S | | D06136J | 1 | | | 275-299 | |
| 006 | 20 | | PA | 18-0 | 35-21-12 | GD00760 | | D.. | 2 | | D06136J | 2 | | | 275-299 | |
| 008 | 20 | | PA | 3-0 | 35-21-12 | D00936 | | 1 | | | SM00003 | | S | | 050-099 | |
| 008 | 20 | | PA | 10-0 | 35-21-12 | D00936 | | 1 | | | SM00002 | | S | | 150-199 | |
| 008 | 20 | | PA | 4-0 | 35-21-12 | D00936 | | 1 | | | SM00003 | | S | | 275-299 | |
| 009 | 20 | | PA | 4-0 | 35-21-12 | D00936 | | 2 | | | GD00002 | D.. | 2 | | ALL | |
| 010 | 20 | | PA | 4-0 | 35-21-12 | SM00003 | | | S | | D00934 | 1 | | | 050-099 | |
| 010 | 20 | | PA | 12-0 | 35-21-12 | SM00002 | | | S | | D00934 | 1 | | | 150-199 | |
| 010 | 20 | | PA | 6-0 | 35-21-12 | SM00003 | | | S | | D00934 | 1 | | | 275-299 | |
| 011 | 20 | | PA | 6-0 | 35-21-12 | GD00760 | | D.. | 2 | | D00934 | 2 | | | ALL | |
| 023 | 20 | | PA | 12-0 | 35-21-14 | D00206 | | 1 | | | D05448P | 3 | | | 275-299 | |
| 030 | 20 | | PA | 10-0 | 35-21-14 | D00206 | | 2 | | | GD00760 | D.. | 2 | | 275-299 | |
| 035 | 20 | | PA | 17-0 | 35-21-12 | D00938 | | 1 | | | SM00003 | | S | | 280-299 | |
| 036 | 20 | | PA | 9-0 | 35-21-12 | D00938 | | 2 | | | GD04194 | D.. | 2 | | 280-299 | |
| 039 | 20 | | PA | 11-0 | 35-21-12 | SM00002 | | | S | | SP03638 | | S | | 150-199 | |
| 040 | 20 | | PA | 13-0 | 35-21-13 | D05448P | | 2 | | | SP03640 | | S | | 050-099, 150-199 | |
| 045 | 18 | | PA | 9-0 | 33-22-31 | D05448P | | 4 | | | D06136J | 3 | DK | | 275-299 | |
| 046 | 18 | | PA | 2-10 | 33-22-31 | D06136J | | 4 | DK | | GD03932 | A.. | 2 | | 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0714 | 286T0714 | | | LEFT AND CENTER AND RIGHT FWD OXYGEN DEPLOYMENT (continued) | | | | | | | | | | | |
| 047 | 18 | | PA | | 2-10 | 33-22-31 | D06136J | 5 | DK | | GD03932 | A.. | 2 | | 275-299 |
| 048 | 20 | | PA | | 10-0 | 33-24-12 | D05448P | 6 | | | D06136J | 6 | | | 275-276, 280-299 |
| 048 | 20 | | PQ | BW | 10-0 | 33-24-12 | D05448P | 6 | | | D06136J | 6 | | | 277-278 |
| 048Z | | | | BW | 0-0 | 33-24-12 | D05448P | | DED | | D06136J | DED | | | 277-278 |
| 049 | 20 | | PA | | 10-0 | 33-24-12 | D05448P | 7 | | | D06136J | 7 | | | 275-276, 280-299 |
| 049 | 20 | | PQ | BX | 10-0 | 33-24-12 | D05448P | 7 | | | D06136J | 7 | | | 277-278 |
| 049Z | | | | BX | 0-0 | 33-24-12 | D05448P | | DED | | D06136J | DED | | | 277-278 |
| 050 | 20 | | PA | | 2-10 | 33-24-12 | D06136J | 8 | | | GD03932 | A.. | 2 | | 275-276, 280-299 |
| 050 | 20 | | PQ | BY | 2-10 | 33-24-12 | D06136J | 8 | | | GD03932 | A.. | 2 | | 277-278 |
| 050Z | | | | BY | 0-0 | 33-24-12 | D06136J | | DED | | GD03932 | DED | | | 277-278 |
| W0718 | 286T0718 | | | LEFT MID OXYGEN LATCHES | | | | | | | | | | | |
| 001 | 14 | | PA | | 57-5 | 35-21-12 | D05740P | 1 | | | D06644J | 1 | FO | | 150-199 |
| 001 | 14 | | PA | | 41-1 | 35-21-12 | D05740P | 1 | | | D06644J | 1 | FO | | 275-278 |
| 001 | 14 | | PA | | 51-9 | 35-21-12 | D05740P | 1 | | | D06644J | 1 | FO | | 280-299 |
| 002 | 16 | | PA | | 6-9 | 35-21-12 | D05740P | 2 | | | SM00001 | | S | | 050-099 |
| 002 | 14 | | PA | | 9-8 | 35-21-12 | D05740P | 2 | | | SM00001 | | S | | 150-199 |
| 002 | 14 | | PA | | 9-2 | 35-21-12 | D05740P | 2 | | | SM00001 | | S | | 275-278 |
| 002 | 14 | | PA | | 9-4 | 35-21-12 | D05740P | 2 | | | SM00001 | | S | | 280-299 |
| 003 | 16 | | PA | | 4-2 | 35-21-12 | SM00002 | | S | | SM00001 | | S | | 050-099 |
| 003 | 14 | | PA | | 4-2 | 35-21-12 | SM00002 | | S | | SM00001 | | S | | 150-199 |
| 003 | 14 | | PA | | 2-10 | 35-21-12 | SM00002 | | S | | SM00001 | | S | | 275-278 |
| 003 | 14 | | PA | | 5-11 | 35-21-12 | SM00002 | | S | | SM00001 | | S | | 280-299 |
| 004 | 20 | | PA | | 4-1 | 35-21-12 | D00146 | 1 | | | SM00001 | | S | | 050-099 |
| 004 | 20 | | PA | | 1-7 | 35-21-12 | D00146 | 1 | | | SM00001 | | S | | 150-199 |
| 004 | 20 | | PA | | 1-4 | 35-21-12 | D00146 | 1 | | | SM00001 | | S | | 275-278 |
| 004 | 20 | | PA | | 3-1 | 35-21-12 | D00146 | 1 | | | SM00001 | | S | | 280-299 |
| 005 | 20 | | PA | | 7-8 | 35-21-12 | D00146 | 2 | | | GD01854 | D.. | E | * | 050-099 |
| 005 | 20 | | PA | | 2-4 | 35-21-12 | D00146 | 2 | | | GD05704 | D.. | E | | 150-199 |
| 005 | 20 | | PA | | 1-9 | 35-21-12 | D00146 | 2 | | | GD05158 | D.. | E | | 275-278 |
| 005 | 20 | | PA | | 1-11 | 35-21-12 | D00146 | 2 | | | GD05158 | D.. | E | | 280-299 |
| 006 | 16 | | PA | | 7-1 | 35-21-12 | SM00002 | | S | | SM00004 | | S | | 050-099 |
| 006 | 14 | | PA | | 6-2 | 35-21-12 | SM00002 | | S | | SM00004 | | S | | 150-199 |
| 006 | 14 | | PA | | 8-4 | 35-21-12 | SM00002 | | S | | SM00004 | | S | | 275-278 |
| 006 | 14 | | PA | | 5-3 | 35-21-12 | SM00002 | | S | | SM00004 | | S | | 280-299 |
| 007 | 20 | | PA | | 2-11 | 35-21-12 | SM00002 | | S | | D01044 | | 1 | | 050-099 |
| 007 | 20 | | PA | | 1-11 | 35-21-12 | SM00002 | | S | | D01044 | | 1 | | 150-199 |
| 007 | 20 | | PA | | 1-6 | 35-21-12 | SM00002 | | S | | D01044 | | 1 | | 275-278 |
| 007 | 20 | | PA | | 2-5 | 35-21-12 | SM00002 | | S | | D01044 | | 1 | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 17

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0718 | 286T0718 | | | LEFT MID OXYGEN LATCHES (continued) | | | | | | | | | | | |
| 008 | 20 | | PA | | 6-2 | 35-21-12 | GD01854 | D.. | E | * | D01044 | | | | 050-099 |
| 008 | 20 | | PA | | 2-10 | 35-21-12 | GD05704 | D.. | E | | D01044 | | | | 150-199 |
| 008 | 20 | | PA | | 3-3 | 35-21-12 | GD05158 | D.. | E | | D01044 | | | | 275-278 |
| 008 | 20 | | PA | | 3-4 | 35-21-12 | GD05158 | D.. | E | | D01044 | | | | 280-299 |
| 010 | 20 | | PA | | 4-4 | 35-21-12 | SM00002 | | S | | D01134 | | | | 050-099 |
| 010 | 20 | | PA | | 1-9 | 35-21-12 | SM00002 | | S | | D01134 | | | | 150-199 |
| 010 | 20 | | PA | | 3-4 | 35-21-12 | SM00002 | | S | | D01134 | | | | 275-278 |
| 010 | 20 | | PA | | 1-11 | 35-21-12 | SM00002 | | S | | D01134 | | | | 280-299 |
| 011 | 20 | | PA | | 4-2 | 35-21-12 | GD01854 | D.. | E | | D01134 | | | | 050-099 |
| 011 | 20 | | PA | | 4-1 | 35-21-12 | GD01854 | D.. | E | | D01134 | | | | 150-199 |
| 011 | 20 | | PA | | 4-0 | 35-21-12 | GD01854 | D.. | E | | D01134 | | | | 275-278 |
| 011 | 20 | | PA | | 4-3 | 35-21-12 | GD01854 | D.. | E | | D01134 | | | | 280-299 |
| 012 | 16 | | PA | | 5-8 | 35-21-12 | SM00004 | | S | | SM00006 | | S | | 050-099 |
| 012 | 14 | | PA | | 7-2 | 35-21-12 | SM00004 | | S | | SM00006 | | S | | 150-199 |
| 012 | 14 | | PA | | 5-2 | 35-21-12 | SM00004 | | S | | SM00006 | | S | | 275-278 |
| 012 | 14 | | PA | | 6-4 | 35-21-12 | SM00004 | | S | | SM00006 | | S | | 280-299 |
| 013 | 20 | | PA | | 1-10 | 35-21-12 | SM00004 | | S | | D00148 | | | 1 | 050-099 |
| 013 | 20 | | PA | | 2-11 | 35-21-12 | SM00004 | | S | | D00148 | | | 1 | 150-199, 275-278 |
| 013 | 20 | | PA | | 1-9 | 35-21-12 | SM00004 | | S | | D00148 | | | 1 | 280-299 |
| 014 | 20 | | PA | | 1-7 | 35-21-12 | GD01854 | D.. | E | | D00148 | | | 2 | 050-099 |
| 014 | 20 | | PA | | 1-10 | 35-21-12 | GD01854 | D.. | E | | D00148 | | | 2 | 150-199, 280-299 |
| 014 | 20 | | PA | | 1-8 | 35-21-12 | GD01854 | D.. | E | | D00148 | | | 2 | 275-278 |
| 016 | 20 | | PA | | 4-4 | 35-21-12 | SM00004 | | S | | D00150 | | | 1 | 050-099 |
| 016 | 20 | | PA | | 1-11 | 35-21-12 | SM00004 | | S | | D00150 | | | 1 | 150-199 |
| 016 | 20 | | PA | | 1-8 | 35-21-12 | SM00004 | | S | | D00150 | | | 1 | 275-278 |
| 016 | 20 | | PA | | 2-10 | 35-21-12 | SM00004 | | S | | D00150 | | | 1 | 280-299 |
| 017 | 20 | | PA | | 4-2 | 35-21-12 | GD01854 | D.. | E | | D00150 | | | 2 | 050-099 |
| 017 | 20 | | PA | | 4-3 | 35-21-12 | GD01854 | D.. | E | | D00150 | | | 2 | 150-199 |
| 017 | 20 | | PA | | 3-9 | 35-21-12 | GD01854 | D.. | E | | D00150 | | | 2 | 275-278 |
| 017 | 20 | | PA | | 3-11 | 35-21-12 | GD01854 | D.. | E | | D00150 | | | 2 | 280-299 |
| 018 | 20 | | PA | | 2-8 | 35-21-12 | SM00006 | | S | | D00152 | | | 1 | 050-099 |
| 018 | 20 | | PA | | 3-2 | 35-21-12 | SM00006 | | S | | D00152 | | | 1 | 150-199 |
| 018 | 20 | | PA | | 1-8 | 35-21-12 | SM00006 | | S | | D00152 | | | 1 | 275-278 |
| 018 | 20 | | PA | | 2-1 | 35-21-12 | SM00006 | | S | | D00152 | | | 1 | 280-299 |
| 019 | 20 | | PA | | 4-2 | 35-21-12 | GD01860 | D.. | E | | D00152 | | | 2 | 050-099, 275-278 |
| 019 | 20 | | PA | | 4-3 | 35-21-12 | GD01860 | D.. | E | | D00152 | | | 2 | 150-199 |
| 019 | 20 | | PA | | 4-8 | 35-21-12 | GD01860 | D.. | E | | D00152 | | | 2 | 280-299 |
| 020 | 16 | | PA | | 6-4 | 35-21-12 | SM00006 | | S | | SM00008 | | S | | 050-099 |
| 020 | 14 | | PA | | 4-9 | 35-21-12 | SM00006 | | S | | SM00008 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 18

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0718 | 286T0718 | | | LEFT MID OXYGEN LATCHES (continued) | | | | | | | | | | | |
| 020 | 14 | PA | | | 8-2 | 35-21-12 | SM00006 | | | | S | | | | 275-278 |
| 020 | 14 | PA | | | 7-1 | 35-21-12 | SM00006 | | | | S | | | | 280-299 |
| 021 | 20 | PA | | | 5-1 | 35-21-12 | D00154 | | 1 | | | | | | 050-099 |
| 021 | 20 | PA | | | 1-9 | 35-21-12 | D00154 | | 1 | | | | | | 150-199 |
| 021 | 20 | PA | | | 3-3 | 35-21-12 | D00154 | | 1 | | | | | | 275-299 |
| 022 | 20 | PA | | | 1-8 | 35-21-12 | GD01860 | | | D.. | E | | 2 | | 050-099 |
| 022 | 20 | PA | | | 1-9 | 35-21-12 | GD01860 | | | D.. | E | | 2 | | 150-199, 280-299 |
| 022 | 20 | PA | | | 1-7 | 35-21-12 | GD01860 | | | D.. | E | | 2 | | 275-278 |
| 024 | 20 | PA | | | 2-9 | 35-21-12 | D01144 | | 1 | | | | | S | 050-099 |
| 024 | 20 | PA | | | 1-5 | 35-21-12 | D01144 | | 1 | | | | | S | 150-199 |
| 024 | 20 | PA | | | 3-3 | 35-21-12 | D01144 | | 1 | | | | | S | 275-278 |
| 024 | 20 | PA | | | 2-1 | 35-21-12 | D01144 | | 1 | | | | | S | 280-299 |
| 025 | 20 | PA | | | 4-0 | 35-21-12 | D01144 | | 2 | | | D.. | E | | 050-099 |
| 025 | 20 | PA | | | 4-1 | 35-21-12 | D01144 | | 2 | | | D.. | E | | 150-199 |
| 025 | 20 | PA | | | 3-6 | 35-21-12 | D01144 | | 2 | | | D.. | E | | 275-278 |
| 025 | 20 | PA | | | 3-11 | 35-21-12 | D01144 | | 2 | | | D.. | E | | 280-299 |
| 026 | 16 | PA | | | 7-8 | 35-21-12 | SM00008 | | | | S | | | S | 050-099 |
| 026 | 14 | PA | | | 7-2 | 35-21-12 | SM00008 | | | | S | | | S | 150-199 |
| 026 | 14 | PA | | | 5-3 | 35-21-12 | SM00008 | | | | S | | | S | 275-278 |
| 026 | 14 | PA | | | 7-1 | 35-21-12 | SM00008 | | | | S | | | S | 280-299 |
| 027 | 20 | PA | | | 5-1 | 35-21-12 | D01146 | | 1 | | | | | S | 050-099 |
| 027 | 20 | PA | | | 3-5 | 35-21-12 | D01146 | | 1 | | | | | S | 150-199 |
| 027 | 20 | PA | | | 1-11 | 35-21-12 | D01146 | | 1 | | | | | S | 275-278 |
| 027 | 20 | PA | | | 3-4 | 35-21-12 | D01146 | | 1 | | | | | S | 280-299 |
| 028 | 20 | PA | | | 4-2 | 35-21-12 | D01146 | | 2 | | | D.. | E | | 050-099 |
| 028 | 20 | PA | | | 4-3 | 35-21-12 | D01146 | | 2 | | | D.. | E | | 150-199 |
| 028 | 20 | PA | | | 4-1 | 35-21-12 | D01146 | | 2 | | | D.. | E | | 275-278 |
| 028 | 20 | PA | | | 16-4 | 35-21-12 | D01146 | | 2 | | | D.. | E | | 280-299 |
| 030 | 20 | PA | | | 2-1 | 35-21-12 | D01148 | | 1 | | | | | S | 050-099 |
| 030 | 20 | PA | | | 8-4 | 35-21-12 | D13634 | | 1 | | | | | S | 150-199 |
| 030 | 20 | PA | | | 1-11 | 35-21-12 | D01148 | | 1 | | | | | S | 275-278 |
| 030 | 20 | PA | | | 2-2 | 35-21-12 | D01148 | | 1 | | | | | S | 280-299 |
| 031 | 20 | PA | | | 1-10 | 35-21-12 | D01148 | | 2 | | | D.. | E | | 050-099 |
| 031 | 20 | PA | | | 2-10 | 35-21-12 | D13634 | | 2 | | | D.. | E | | 150-199 |
| 031 | 20 | PA | | | 3-1 | 35-21-12 | D01148 | | 2 | | | D.. | E | | 275-278 |
| 031 | 20 | PA | | | 4-0 | 35-21-12 | D01148 | | 2 | | | D.. | E | | 280-299 |
| 033 | 20 | PA | | | 4-5 | 35-21-12 | SM00010 | | | | S | | | 1 | 050-099 |
| 033 | 20 | PA | | | 2-10 | 35-21-12 | SM00012 | | | | S | | | 1 | 150-199 |
| 034 | 20 | PA | | | 4-3 | 35-21-12 | GD01866 | | | D.. | E | | | 2 | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 19

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0718 | 286T0718 | | | LEFT MID OXYGEN LATCHES (continued) | | | | | | | | | | | | |
| 034 | 20 | | PA | 3-11 | 35-21-12 | GD05708 | D.. | E | | D01150 | 2 | | | 150-199 | | |
| 035 | 16 | | PA | 6-5 | 35-21-12 | SM00012 | | S | | SM00014 | | S | | 050-099 | | |
| 035 | 14 | | PA | 5-9 | 35-21-12 | SM00012 | | S | | D06644J | 2 | FN | | 150-199 | | |
| 036 | 20 | | PA | 2-10 | 35-21-12 | SM00012 | | S | | D01152 | 1 | | | 050-099 | | |
| 036 | 20 | | PA | 2-8 | 35-21-12 | SM00012 | | S | | D01152 | 1 | | | 150-199 | | |
| 037 | 20 | | PA | 4-5 | 35-21-12 | GD01872 | D.. | E | | D01152 | 2 | | | 050-099 | | |
| 037 | 20 | | PA | 2-8 | 35-21-12 | GD05708 | D.. | E | | D01152 | 2 | | | 150-199 | | |
| 039 | 20 | | PA | 6-1 | 35-21-12 | SM00012 | | S | | D01154 | 1 | | | 050-099 | | |
| 040 | 20 | | PA | 1-8 | 35-21-12 | GD01872 | D.. | E | | D01154 | 2 | | | 050-099 | | |
| 041 | 16 | | PA | 13-1 | 35-21-12 | SM00014 | | S | | SM00016 | | S | | 050-099 | | |
| 042 | 20 | | PA | 3-2 | 35-21-12 | SM00014 | | S | | D01156 | 1 | | | 050-099 | | |
| 043 | 20 | | PA | 4-0 | 35-21-12 | GD01872 | D.. | E | | D01156 | 2 | | | 050-099 | | |
| 047 | 20 | | PA | 4-7 | 35-21-12 | SM00016 | | S | | D01160 | 1 | | | 050-099 | | |
| 048 | 20 | | PA | 2-8 | 35-21-12 | GD00683 | D.. | E | | D01160 | 2 | | | 050-099 | | |
| 049 | 16 | | PA | 13-3 | 35-21-12 | SM00018 | | S | | SM00016 | | S | | 050-099 | | |
| 050 | 20 | | PA | 14-10 | 35-21-12 | SM00016 | | S | | D01180 | 1 | | | 050-099 | | |
| 051 | 20 | | PA | 5-1 | 35-21-12 | GD01830 | D.. | E | | D01180 | 2 | | | 050-099 | | |
| 053 | 20 | | PA | 1-8 | 35-21-12 | SM00018 | | S | | D01182 | 1 | | | 050-099 | | |
| 054 | 20 | | PA | 3-7 | 35-21-12 | GD01830 | D.. | E | | D01182 | 2 | | | 050-099 | | |
| 055 | 16 | | PA | 4-4 | 35-21-12 | SM00020 | | S | | SM00018 | | S | | 050-099 | | |
| 056 | 20 | | PA | 3-1 | 35-21-12 | SM00018 | | S | | D01184 | 1 | | | 050-099 | | |
| 057 | 20 | | PA | 2-3 | 35-21-12 | GD01830 | D.. | E | | D01184 | 2 | | | 050-099 | | |
| 059 | 20 | | PA | 1-9 | 35-21-12 | SM00020 | | S | | D01186 | 1 | | | 050-099 | | |
| 060 | 20 | | PA | 4-0 | 35-21-12 | GD01836 | D.. | E | | D01186 | 2 | | | 050-099 | | |
| 062 | 20 | | PA | 4-5 | 35-21-12 | SM00020 | | S | | D01188 | 1 | | | 050-099 | | |
| 063 | 20 | | PA | 1-8 | 35-21-12 | GD01836 | D.. | E | | D01188 | 2 | | | 050-099 | | |
| 064 | 20 | | PA | 3-11 | 35-21-12 | GD01836 | D.. | E | | D01190 | 2 | | | 050-099 | | |
| 065 | 16 | | PA | 5-6 | 35-21-12 | SM00010 | | S | | SM00012 | | S | | 050-099 | | |
| 065 | 14 | | PA | 14-1 | 35-21-12 | SM00010 | | S | | SM00012 | | S | | 150-199 | | |
| 065 | 14 | | PA | 3-5 | 35-21-12 | SM00010 | | S | | D06644J | 2 | FO | | 275-278 | | |
| 065 | 14 | | PA | 2-0 | 35-21-12 | SM00010 | | S | | D06644J | 2 | FO | | 280-299 | | |
| 066 | 16 | | PA | 7-2 | 35-21-12 | SM00020 | | S | | D01190 | 1 | FM | | 050-099 | | |
| 068 | 20 | | PA | 3-9 | 35-21-12 | D00940 | | 1 | | SM00001 | | S | | 275-278 | | |
| 068 | 20 | | PA | 1-8 | 35-21-12 | D00940 | | 1 | | SM00001 | | S | | 280-299 | | |
| 069 | 20 | | PA | 4-4 | 35-21-12 | D00940 | | 2 | | GD05158 | | D.. | E | 275-278 | | |
| 069 | 20 | | PA | 4-2 | 35-21-12 | D00940 | | 2 | | GD05158 | | D.. | E | 280-299 | | |
| 074 | 14 | | PA | 8-0 | 35-21-12 | SM00024 | | S | | SM00026 | | S | | 150-199 | | |
| 074 | 14 | | PA | 6-2 | 35-21-12 | SM00024 | | S | | SM00026 | | S | | 275-278 | | |
| 074 | 14 | | PA | 25-11 | 35-21-12 | SM00024 | | S | | SM00026 | | S | | 280-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0710

Page 20

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0718 | 286T0718 | | | LEFT MID OXYGEN LATCHES (continued) | | | | | | | | | | | | |
| 076 | 14 | | PA | 5-10 | 35-21-12 | SM00026 | | | | | S | | SM00010 | | S | 150-199 |
| 076 | 14 | | PA | 4-11 | 35-21-12 | SM00026 | | | | | S | | SM00010 | | S | 275-278 |
| 076 | 14 | | PA | 5-4 | 35-21-12 | SM00026 | | | | | S | | SM00010 | | S | 280-299 |
| 078 | 20 | | PA | 1-6 | 35-21-12 | D11318 | | | 1 | | | | SM00024 | | S | 150-199 |
| 078 | 20 | | PA | 1-9 | 35-21-12 | D11318 | | | 1 | | | | SM00024 | | S | 275-299 |
| 079 | 20 | | PA | 1-10 | 35-21-12 | D11318 | | | 2 | | | | GD04998 | D.. | E | 150-199 |
| 079 | 20 | | PA | 1-8 | 35-21-12 | D11318 | | | 2 | | | | GD04998 | D.. | E | 275-278 |
| 079 | 20 | | PA | 18-9 | 35-21-12 | D11318 | | | 2 | | | | GD02536 | D.. | E | 280-299 |
| 080 | 20 | | PA | 3-3 | 35-21-12 | D11320 | | | 1 | | | | SM00024 | | S | 150-199 |
| 080 | 20 | | PA | 2-11 | 35-21-12 | D11320 | | | 1 | | | | SM00024 | | S | 275-278 |
| 080 | 20 | | PA | 2-8 | 35-21-12 | D11320 | | | 1 | | | | SM00024 | | S | 280-299 |
| 081 | 20 | | PA | 4-2 | 35-21-12 | D11320 | | | 2 | | | | GD04998 | D.. | E | 150-199 |
| 081 | 20 | | PA | 3-8 | 35-21-12 | D11320 | | | 2 | | | | GD04998 | D.. | E | 275-278 |
| 081 | 20 | | PA | 20-9 | 35-21-12 | D11320 | | | 2 | | | | GD02536 | D.. | E | 280-299 |
| 082 | 20 | | PA | 1-8 | 35-21-12 | D11322 | | | 1 | | | | SM00026 | | S | 150-199 |
| 082 | 20 | | PA | 1-7 | 35-21-12 | D11322 | | | 1 | | | | SM00026 | | S | 275-278 |
| 082 | 20 | | PA | 2-11 | 35-21-12 | D11322 | | | 1 | | | | SM00026 | | S | 280-299 |
| 083 | 20 | | PA | 2-2 | 35-21-12 | D11322 | | | 2 | | | | GD05706 | D.. | E | 150-199 |
| 083 | 20 | | PA | 4-5 | 35-21-12 | D11322 | | | 2 | | | | GD05002 | D.. | E | 275-278 |
| 083 | 20 | | PA | 4-4 | 35-21-12 | D11322 | | | 2 | | | | GD05002 | D.. | E | 280-299 |
| 084 | 20 | | PA | 3-1 | 35-21-12 | D11324 | | | 1 | | | | SM00026 | | S | 275-278 |
| 084 | 20 | | PA | 2-0 | 35-21-12 | D11324 | | | 1 | | | | SM00026 | | S | 280-299 |
| 085 | 20 | | PA | 2-2 | 35-21-12 | D11324 | | | 2 | | | | GD05002 | D.. | E | 275-278 |
| 085 | 20 | | PA | 1-10 | 35-21-12 | D11324 | | | 2 | | | | GD05002 | D.. | E | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0710
Page 21 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|----------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|---------|------------------|---------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0720 | 286T0720 | | | CENTER MID OXYGEN LATCHES | | | | | | | | | | | | | | |
| 001 | 16 | | PA | 57-0 | 35-21-14 | D05750P | | | | | | | | | | 050-099 | | |
| 001 | 14 | | PA | 72-0 | 35-21-14 | D05750P | | | | | | | | | 1 | FO | 150-199, 275-299 | |
| 002 | 16 | | PA | 10-0 | 35-21-14 | D05750P | | | | | | | | | 1 | | 050-099 | |
| 002 | 14 | | PA | 9-10 | 35-21-14 | D05750P | | | | | | | | | 1 | FO | 150-199, 275-299 | |
| 067 | 16 | | PA | 57-0 | 35-21-12 | D05750P | | | | | | | | | 2 | | 050-099 | |
| 068 | 16 | | PA | 57-0 | 35-21-13 | D05750P | | | | | | | | | 3 | | 050-099 | |
| W0721 | 286T0721 | | | E1-2 TO E2-5 SHELF | | | | | | | | | | | | | | |
| 001 | 22 | | PA | 8-0 | 23-22-11 | D04751J | | | | | | | | | | | ALL | |
| 002 | 24 | | PK | 8-0 | SPARE | D04751J | | | | | | | | | 2 | | 150-199, 275-278 | |
| 002 | 24 | | PK | 8-0 | 23-22-11 | D04751J | | | | | | | | | 2 | | 280-299 | |
| 003 | 24 | | PK | 8-0 | SPARE | D04751J | | | | | | | | | 3 | | 150-199, 275-278 | |
| 003 | 24 | | PK | 8-0 | 23-22-11 | D04751J | | | | | | | | | 3 | | 280-299 | |
| 004 | 24 | | PK | 8-0 | SPARE | D04751J | | | | | | | | | 4 | | 150-199, 275-299 | |
| 005 | 24 | | PK | 8-0 | SPARE | D04751J | | | | | | | | | 5 | | 150-199, 275-299 | |
| 006 | 22 | | PA | 8-0 | SPARE | D04751J | | | | | | | | | 6 | | ALL | |
| W0722 | 286T0722 | | | RIGHT MID OXYGEN LATCHES | | | | | | | | | | | | | | |
| 001 | 14 | | PA | 65-4 | 35-21-13 | D05746P | | | | | | | | | 1 | FO | 150-199 | |
| 001 | 14 | | PA | 47-9 | 35-21-13 | D05746P | | | | | | | | | 1 | FO | 275-278 | |
| 001 | 14 | | PA | 58-2 | 35-21-13 | D05746P | | | | | | | | | 1 | FO | 280-299 | |
| 002 | 16 | | PA | 20-3 | 35-21-13 | D05746P | | | | | | | | | | S | 050-099 | |
| 002 | 14 | | PA | 15-10 | 35-21-13 | D05746P | | | | | | | | | | S | 150-157 | |
| 002 | 14 | | PA | 20-3 | 35-21-13 | D05746P | | | | | | | | | | S | 162-199 | |
| 002 | 14 | | PA | 16-6 | 35-21-13 | D05746P | | | | | | | | | | S | 275-278 | |
| 002 | 14 | | PA | 17-3 | 35-21-13 | D05746P | | | | | | | | | | S | 280-299 | |
| 004 | 20 | | PA | 3-4 | 35-21-13 | D01002 | | | | | | | | | | S | 150-157 | |
| 004 | 20 | | PA | 1-6 | 35-21-13 | D01002 | | | | | | | | | | S | 275-278 | |
| 004 | 20 | | PA | 1-11 | 35-21-13 | D01002 | | | | | | | | | | S | 280-299 | |
| 005 | 20 | | PA | 2-4 | 35-21-13 | D01002 | | | | | | | | | | D.. | E | 150-157 |
| 005 | 20 | | PA | 1-10 | 35-21-13 | D01002 | | | | | | | | | | D.. | E | 275-278 |
| 005 | 20 | | PA | 1-9 | 35-21-13 | D01002 | | | | | | | | | | D.. | E | 280-299 |
| 006 | 14 | | PA | 5-11 | 35-21-13 | SM00002 | | | | | | | | | | | S | 150-157 |
| 006 | 14 | | PA | 2-6 | 35-21-13 | SM00002 | | | | | | | | | | | S | 275-278 |
| 006 | 14 | | PA | 4-9 | 35-21-13 | SM00002 | | | | | | | | | | | S | 280-299 |
| 007 | 20 | | PA | 1-5 | 35-21-13 | SM00003 | | | | | | | | | | | 1 | 050-099 |
| 007 | 20 | | PA | 2-0 | 35-21-13 | SM00003 | | | | | | | | | | | 1 | 150-199 |
| 007 | 20 | | PA | 1-7 | 35-21-13 | SM00003 | | | | | | | | | | | 1 | 275-278 |
| 007 | 20 | | PA | 2-4 | 35-21-13 | SM00003 | | | | | | | | | | | 1 | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0722 | 286T0722 | | | RIGHT MID OXYGEN LATCHES (continued) | | | | | | | | | | | |
| 008 | 20 | | PA | | 6-1 | 35-21-13 | GD01972 | D.. | E | | D02276 | | | | 050-099 |
| 008 | 20 | | PA | | 2-9 | 35-21-13 | GD05710 | D.. | E | | D02276 | | | | 150-157 |
| 008 | 20 | | PA | | 6-0 | 35-21-13 | GD01972 | D.. | E | | D02276 | | | | 162-199 |
| 008 | 20 | | PA | | 3-7 | 35-21-13 | GD05154 | D.. | E | | D02276 | | | | 275-278 |
| 008 | 20 | | PA | | 3-3 | 35-21-13 | GD05154 | D.. | E | | D02276 | | | | 280-299 |
| 009 | 16 | | PA | | 6-4 | 35-21-13 | SM00003 | | S | | SM00005 | | S | | 050-099 |
| 009 | 14 | | PA | | 5-4 | 35-21-13 | SM00003 | | S | | SM00005 | | S | | 150-199 |
| 009 | 14 | | PA | | 8-2 | 35-21-13 | SM00003 | | S | | SM00005 | | S | | 275-278 |
| 009 | 14 | | PA | | 6-5 | 35-21-13 | SM00003 | | S | | SM00005 | | S | | 280-299 |
| 010 | 20 | | PA | | 2-7 | 35-21-13 | SM00003 | | S | | D01046 | | 1 | | 050-099 |
| 010 | 20 | | PA | | 1-8 | 35-21-13 | SM00003 | | S | | D01046 | | 1 | | 150-199 |
| 010 | 20 | | PA | | 3-0 | 35-21-13 | SM00003 | | S | | D01046 | | 1 | | 275-278 |
| 010 | 20 | | PA | | 1-11 | 35-21-13 | SM00003 | | S | | D01046 | | 1 | | 280-299 |
| 011 | 20 | | PA | | 4-2 | 35-21-13 | GD01972 | D.. | E | | D01046 | | 2 | | 050-099 |
| 011 | 20 | | PA | | 4-3 | 35-21-13 | GD01972 | D.. | E | | D01046 | | 2 | | 150-199, 275-299 |
| 013 | 20 | | PA | | 1-10 | 35-21-13 | SM00005 | | S | | D01048 | | 1 | | 050-099 |
| 013 | 20 | | PA | | 2-1 | 35-21-13 | SM00005 | | S | | D01048 | | 1 | | 150-199 |
| 013 | 20 | | PA | | 3-1 | 35-21-13 | SM00005 | | S | | D01048 | | 1 | | 275-278 |
| 013 | 20 | | PA | | 2-11 | 35-21-13 | SM00005 | | S | | D01048 | | 1 | | 280-299 |
| 014 | 20 | | PA | | 1-8 | 35-21-13 | GD01972 | D.. | E | | D01048 | | 2 | | 050-099 |
| 014 | 20 | | PA | | 1-10 | 35-21-13 | GD01972 | D.. | E | | D01048 | | 2 | | 150-199, 275-278 |
| 014 | 20 | | PA | | 1-9 | 35-21-13 | GD01972 | D.. | E | | D01048 | | 2 | | 280-299 |
| 015 | 16 | | PA | | 6-5 | 35-21-13 | SM00005 | | S | | SM00007 | | S | | 050-099 |
| 015 | 14 | | PA | | 6-2 | 35-21-13 | SM00005 | | S | | SM00007 | | S | | 150-199, 275-278 |
| 015 | 14 | | PA | | 6-4 | 35-21-13 | SM00005 | | S | | SM00007 | | S | | 280-299 |
| 016 | 20 | | PA | | 2-10 | 35-21-13 | SM00005 | | S | | D01050 | | 1 | | 050-099 |
| 016 | 20 | | PA | | 2-9 | 35-21-13 | SM00005 | | S | | D01050 | | 1 | | 150-199 |
| 016 | 20 | | PA | | 1-7 | 35-21-13 | SM00005 | | S | | D01050 | | 1 | | 275-278 |
| 016 | 20 | | PA | | 1-8 | 35-21-13 | SM00005 | | S | | D01050 | | 1 | | 280-299 |
| 017 | 20 | | PA | | 3-11 | 35-21-13 | GD01972 | D.. | E | | D01050 | | 2 | | 050-099, 275-299 |
| 017 | 20 | | PA | | 4-1 | 35-21-13 | GD01972 | D.. | E | | D01050 | | 2 | | 150-199 |
| 018 | 20 | | PA | | 1-9 | 35-21-13 | SM00007 | | S | | D01052 | | 1 | | 050-099 |
| 018 | 20 | | PA | | 1-10 | 35-21-13 | SM00007 | | S | | D01052 | | 1 | | 150-199 |
| 018 | 20 | | PA | | 2-9 | 35-21-13 | SM00007 | | S | | D01052 | | 1 | | 275-278 |
| 018 | 20 | | PA | | 2-10 | 35-21-13 | SM00007 | | S | | D01052 | | 1 | | 280-299 |
| 019 | 20 | | PA | | 4-0 | 35-21-13 | GD01978 | D.. | E | | D01052 | | 2 | | 050-099 |
| 019 | 20 | | PA | | 4-3 | 35-21-13 | GD01978 | D.. | E | | D01052 | | 2 | | 150-199, 275-299 |
| 021 | 20 | | PA | | 3-0 | 35-21-13 | SM00007 | | S | | D01054 | | 1 | | 050-099, 150-199 |
| 021 | 20 | | PA | | 2-1 | 35-21-13 | SM00007 | | S | | D01054 | | 1 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0722 | 286T0722 | | | RIGHT MID OXYGEN LATCHES (continued) | | | | | | | | | | | | |
| 022 | 20 | | PA | 1-7 | 35-21-13 | GD01978 | D.. | E | | D01054 | | | 2 | | 050-099 | |
| 022 | 20 | | PA | 1-9 | 35-21-13 | GD01978 | D.. | E | | D01054 | | | 2 | | 150-199, 280-299 | |
| 022 | 20 | | PA | 1-10 | 35-21-13 | GD01978 | D.. | E | | D01054 | | | 2 | | 275-278 | |
| 023 | 16 | | PA | 7-4 | 35-21-13 | SM00009 | | S | | SM00007 | | | | S | 050-099 | |
| 023 | 14 | | PA | 7-5 | 35-21-13 | SM00009 | | S | | SM00007 | | | | S | 150-199 | |
| 023 | 14 | | PA | 5-5 | 35-21-13 | SM00009 | | S | | SM00007 | | | | S | 275-299 | |
| 024 | 20 | | PA | 2-2 | 35-21-13 | SM00009 | | S | | D01056 | | | 1 | | 050-099 | |
| 024 | 20 | | PA | 2-5 | 35-21-13 | SM00009 | | S | | D01056 | | | 1 | | 150-199 | |
| 024 | 20 | | PA | 2-0 | 35-21-13 | SM00009 | | S | | D01056 | | | 1 | | 275-278 | |
| 024 | 20 | | PA | 2-1 | 35-21-13 | SM00009 | | S | | D01056 | | | 1 | | 280-299 | |
| 025 | 20 | | PA | 3-11 | 35-21-13 | GD01978 | D.. | E | | D01056 | | | 2 | | 050-099, 280-299 | |
| 025 | 20 | | PA | 4-0 | 35-21-13 | GD01978 | D.. | E | | D01056 | | | 2 | | 150-199 | |
| 025 | 20 | | PA | 3-10 | 35-21-13 | GD01978 | D.. | E | | D01056 | | | 2 | | 275-278 | |
| 027 | 20 | | PA | 2-7 | 35-21-13 | SM00009 | | S | | D01058 | | | 1 | | 050-099 | |
| 027 | 20 | | PA | 2-6 | 35-21-13 | SM00009 | | S | | D01058 | | | 1 | | 150-199 | |
| 027 | 20 | | PA | 3-1 | 35-21-13 | SM00009 | | S | | D01058 | | | 1 | | 275-299 | |
| 028 | 20 | | PA | 4-2 | 35-21-13 | GD01984 | D.. | E | | D01058 | | | 2 | | 050-099 | |
| 028 | 20 | | PA | 4-3 | 35-21-13 | GD05038 | D.. | E | | D01058 | | | 2 | | 150-199 | |
| 028 | 20 | | PA | 4-4 | 35-21-13 | GD05038 | D.. | E | | D01058 | | | 2 | | 275-278 | |
| 028 | 20 | | PA | 16-3 | 35-21-13 | GD02490 | D.. | E | | D01058 | | | 2 | | 280-299 | |
| 029 | 16 | | PA | 6-4 | 35-21-13 | SM00011 | | S | | SM00009 | | | | S | 050-099 | |
| 029 | 14 | | PA | 7-5 | 35-21-13 | SM00011 | | S | | SM00026 | | | | S | 150-199 | |
| 029 | 14 | | PA | 4-8 | 35-21-13 | SM00011 | | S | | SM00026 | | | | S | 275-278 | |
| 029 | 14 | | PA | 7-2 | 35-21-13 | SM00011 | | S | | SM00026 | | | | S | 280-299 | |
| 031 | 20 | | PA | 2-0 | 35-21-13 | SM00011 | | S | | D01060 | | | 1 | | 050-099, 275-278 | |
| 031 | 20 | | PA | 9-9 | 35-21-13 | SM00011 | | S | | D13648 | | | 1 | | 150-199 | |
| 031 | 20 | | PA | 2-3 | 35-21-13 | SM00011 | | S | | D01060 | | | 1 | | 280-299 | |
| 032 | 20 | | PA | 1-7 | 35-21-13 | GD01984 | D.. | E | | D01060 | | | 2 | | 050-099 | |
| 032 | 20 | | PA | 8-1 | 35-21-13 | GD04978 | D.. | E | | D13648 | | | 2 | | 150-199 | |
| 032 | 20 | | PA | 3-5 | 35-21-13 | GD05042 | D.. | E | | D01060 | | | 2 | | 275-278 | |
| 032 | 20 | | PA | 3-10 | 35-21-13 | GD05042 | D.. | E | | D01060 | | | 2 | | 280-299 | |
| 033 | 16 | | PA | 6-3 | 35-21-13 | SM00011 | | S | | SM00013 | | | | S | 050-099 | |
| 033 | 14 | | PA | 6-3 | 35-21-13 | SM00011 | | S | | SM00013 | | | | S | 150-199 | |
| 033 | 14 | | PA | 3-7 | 35-21-13 | SM00011 | | S | | D06646J | | | 2 | FO | 275-278 | |
| 033 | 14 | | PA | 1-9 | 35-21-13 | SM00011 | | S | | D06646J | | | 2 | FO | 280-299 | |
| 034 | 20 | | PA | 2-8 | 35-21-13 | SM00011 | | S | | D01062 | | | 1 | | 050-099 | |
| 034 | 20 | | PA | 8-10 | 35-21-13 | SM00013 | | S | | D01062 | | | 1 | | 150-199 | |
| 035 | 20 | | PA | 3-10 | 35-21-13 | GD01984 | D.. | E | | D01062 | | | 2 | | 050-099 | |
| 035 | 20 | | PA | 3-11 | 35-21-13 | GD05714 | D.. | E | | D01062 | | | 2 | | 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0722 | 286T0722 | | | RIGHT MID OXYGEN LATCHES (continued) | | | | | | | | | | | |
| 037 | 20 | | PA | | 1-11 | 35-21-13 | SM00013 | | | | D01004 | | | | 050-099 |
| 037 | 20 | | PA | | 11-11 | 35-21-13 | SM00013 | | | | D01004 | | | | 150-199 |
| 038 | 20 | | PA | | 4-4 | 35-21-13 | GD01990 | D.. | E | | D01004 | | | | 050-099 |
| 038 | 20 | | PA | | 2-8 | 35-21-13 | GD05714 | D.. | E | | D01004 | | | | 150-199 |
| 039 | 16 | | PA | | 4-4 | 35-21-13 | SM00013 | | | | SM00015 | | S | | 050-099 |
| 039 | 14 | | PA | | 13-10 | 35-21-13 | SM00013 | | | | D06646J | | FO | | 150-199 |
| 040 | 20 | | PA | | 3-0 | 35-21-13 | SM00013 | | | | D01094 | | | | 050-099 |
| 041 | 20 | | PA | | 1-7 | 35-21-13 | GD01990 | D.. | E | | D01094 | | | | 050-099 |
| 043 | 20 | | PA | | 3-4 | 35-21-13 | SM00015 | | | | D01096 | | | | 050-099 |
| 044 | 20 | | PA | | 3-10 | 35-21-13 | GD01990 | D.. | E | | D01096 | | | | 050-099 |
| 045 | 16 | | PA | | 24-7 | 35-21-13 | SM00015 | | | | SM00017 | | S | | 050-099 |
| 048 | 20 | | PA | | 16-1 | 35-21-13 | SM00017 | | | | D01100 | | | | 050-099 |
| 049 | 20 | | PA | | 2-8 | 35-21-13 | GD04508 | D.. | E | | D01100 | | | | 050-099 |
| 051 | 20 | | PA | | 2-8 | 35-21-13 | SM00017 | | | | D01102 | | | | 050-099 |
| 052 | 20 | | PA | | 4-1 | 35-21-13 | GD02000 | D.. | E | | D01102 | | | | 050-099 |
| 053 | 16 | | PA | | 5-3 | 35-21-13 | SM00019 | | | | SM00017 | | S | | 050-099 |
| 054 | 20 | | PA | | 3-11 | 35-21-13 | SM00019 | | | | D01104 | | | | 050-099 |
| 055 | 20 | | PA | | 1-7 | 35-21-13 | GD02000 | D.. | E | | D01104 | | | | 050-099 |
| 057 | 20 | | PA | | 1-4 | 35-21-13 | SM00019 | | | | D01106 | | | | 050-099 |
| 058 | 20 | | PA | | 4-0 | 35-21-13 | GD02000 | D.. | E | | D01106 | | | | 050-099 |
| 059 | 16 | | PA | | 6-1 | 35-21-13 | SM00021 | | | | SM00019 | | S | | 050-099 |
| 061 | 20 | | PA | | 4-5 | 35-21-13 | SM00021 | | | | D01108 | | | | 050-099 |
| 062 | 20 | | PA | | 4-2 | 35-21-13 | GD02006 | D.. | E | | D01108 | | | | 050-099 |
| 063 | 20 | | PA | | 1-10 | 35-21-13 | SM00021 | | | | D01110 | | | | 050-099 |
| 064 | 20 | | PA | | 1-7 | 35-21-13 | GD02006 | D.. | E | | D01110 | | | | 050-099 |
| 065 | 20 | | PA | | 2-7 | 35-21-13 | SM00021 | | | | D01112 | | | | 050-099 |
| 066 | 20 | | PA | | 3-7 | 35-21-13 | GD02006 | D.. | E | | D01112 | | | | 050-099 |
| 067 | 20 | | PA | | 4-2 | 35-21-13 | D00952 | | 1 | | SM00002 | | | S | 275-278 |
| 067 | 20 | | PA | | 2-10 | 35-21-13 | D00952 | | 1 | | SM00002 | | | S | 280-299 |
| 068 | 20 | | PA | | 4-4 | 35-21-13 | D00952 | | 2 | | GD05154 | | D.. | E | 275-278 |
| 068 | 20 | | PA | | 4-1 | 35-21-13 | D00952 | | 2 | | GD05154 | | D.. | E | 280-299 |
| 073 | 14 | | PA | | 4-10 | 35-21-13 | SM00009 | | | S | SM00024 | | | S | 150-199 |
| 073 | 14 | | PA | | 6-4 | 35-21-13 | SM00009 | | | S | SM00024 | | | S | 275-278 |
| 073 | 14 | | PA | | 6-3 | 35-21-13 | SM00009 | | | S | SM00024 | | | S | 280-299 |
| 075 | 14 | | PA | | 6-2 | 35-21-13 | SM00024 | | | S | SM00026 | | | S | 150-199, 275-278 |
| 075 | 14 | | PA | | 25-1 | 35-21-13 | SM00024 | | | S | SM00026 | | | S | 280-299 |
| 078 | 20 | | PA | | 1-10 | 35-21-13 | SM00024 | | | S | D11266 | | | 1 | 150-199 |
| 078 | 20 | | PA | | 1-9 | 35-21-13 | SM00024 | | | S | D11266 | | | 1 | 275-278 |
| 078 | 20 | | PA | | 1-6 | 35-21-13 | SM00024 | | | S | D11266 | | | 1 | 280-299 |

WIRE LIST

D280T132

91-21-11
 Section W0720
 Page 4
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0722 | 286T0722 | | | RIGHT MID OXYGEN LATCHES (continued) | | | | | | | | | | | | |
| 079 | 20 | | PA | 1-10 | 35-21-13 | GD05038 | D.. | E | | D11266 | 2 | | | 150-199 | | |
| 079 | 20 | | PA | 1-11 | 35-21-13 | GD05038 | D.. | E | | D11266 | 2 | | | 275-278 | | |
| 079 | 20 | | PA | 18-9 | 35-21-13 | GD02490 | D.. | E | | D11266 | 2 | | | 280-299 | | |
| 080 | 20 | | PA | 4-0 | 35-21-13 | SM00024 | | S | | D11268 | 1 | | | 150-199 | | |
| 080 | 20 | | PA | 3-2 | 35-21-13 | SM00024 | | S | | D11268 | 1 | | | 275-278 | | |
| 080 | 20 | | PA | 3-0 | 35-21-13 | SM00024 | | S | | D11268 | 1 | | | 280-299 | | |
| 081 | 20 | | PA | 4-0 | 35-21-13 | GD05038 | D.. | E | | D11268 | 2 | | | 150-199 | | |
| 081 | 20 | | PA | 4-1 | 35-21-13 | GD05038 | D.. | E | | D11268 | 2 | | | 275-278 | | |
| 081 | 20 | | PA | 20-11 | 35-21-13 | GD02490 | D.. | E | | D11268 | 2 | | | 280-299 | | |
| 082 | 20 | | PA | 3-1 | 35-21-13 | SM00026 | | S | | D11270 | 1 | | | 150-199 | | |
| 082 | 20 | | PA | 1-8 | 35-21-13 | SM00026 | | S | | D11270 | 1 | | | 275-299 | | |
| 083 | 20 | | PA | 2-2 | 35-21-13 | GD05712 | D.. | E | | D11270 | 2 | | | 150-199 | | |
| 083 | 20 | | PA | 4-6 | 35-21-13 | GD05042 | D.. | E | | D11270 | 2 | | | 275-278 | | |
| 083 | 20 | | PA | 4-3 | 35-21-13 | GD05042 | D.. | E | | D11270 | 2 | | | 280-299 | | |
| 084 | 20 | | PA | 2-10 | 35-21-13 | SM00026 | | S | | D11272 | 1 | | | 275-278 | | |
| 084 | 20 | | PA | 3-3 | 35-21-13 | SM00026 | | S | | D11272 | 1 | | | 280-299 | | |
| 085 | 20 | | PA | 2-5 | 35-21-13 | GD05042 | D.. | E | | D11272 | 2 | | | 275-278 | | |
| 085 | 20 | | PA | 1-9 | 35-21-13 | GD05042 | D.. | E | | D11272 | 2 | | | 280-299 | | |
| W0723 | 286T0723 | | | IRS-C,SHELF TO SEL PNL | | | | | | | | | | | | |
| 003 | 20 | | PA | 39-3 | 34-21-31 | D04757J | | 3 | | D00743 | 3 | | | ALL | | |
| 004 | 20 | | PA | 39-3 | 34-21-31 | D04757J | | 4 | | D00743 | 4 | | | ALL | | |
| 005 | 20 | | PA | 39-3 | 34-21-31 | D04757J | | 5 | | D00743 | 5 | | | ALL | | |
| 008 | 20 | | PA | 1-6 | 34-21-31 | GD00707 | S.. | E | | D00743 | 8 | | | ALL | | |
| 010 | 22 | | PQ | AJ | 6-9 | 33-16-17 | TB0068Y | C018 | BJ | D00743 | 10 | | | 050-099, 155-199 | | |
| 010 | 22 | | PQ | AJ | 6-4 | 33-16-17 | TB0066Y | C036 | BJ | D00743 | 10 | | | 150-154, 275-299 | | |
| 010Z | | | | AJ | 0-0 | 33-16-17 | TB0068Y | DED | | D00743 | DED | | | 050-099, 155-199 | | |
| 010Z | | | | AJ | 0-0 | 33-16-17 | TB0066Y | DED | | D00743 | DED | | | 150-154, 275-299 | | |
| 012 | 24 | | PK | 39-3 | 34-21-31 | D04757J | | 12 | | D00743 | 12 | | | ALL | | |
| 013 | 24 | | PK | 39-3 | 34-21-31 | D04757J | | 13 | | D00743 | 13 | | | ALL | | |
| 014 | 22 | | PA | 39-3 | 34-21-31 | D04757J | | 14 | | D00743 | 14 | | | ALL | | |
| 015 | 22 | | PA | 39-3 | 34-21-31 | D04757J | | 15 | | D00743 | 15 | | | ALL | | |
| 016 | 22 | | PA | 39-3 | 34-21-31 | D04757J | | 16 | | D00743 | 16 | | | ALL | | |
| 017 | 22 | | PA | 39-3 | 34-21-31 | D04757J | | 17 | | D00743 | 17 | | | ALL | | |
| 018 | 22 | | PA | 6-9 | 33-16-17 | TB0068Y | A018 | BJ | | D00743 | 18 | | | ALL | | |
| 019 | 22 | | PQ | AS | 6-9 | 33-16-17 | TB0068Y | C018 | BJ | D00743 | 11 | | | 050-099, 155-199 | | |
| 019 | 22 | | PQ | AS | 6-4 | 33-16-17 | TB0066Y | C036 | BJ | D00743 | 11 | | | 150-154, 275-299 | | |
| 019Z | | | | AS | 0-0 | 33-16-17 | TB0068Y | DED | | D00743 | DED | | | 050-099, 155-199 | | |
| 019Z | | | | AS | 0-0 | 33-16-17 | TB0066Y | DED | | D00743 | DED | | | 150-154, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0723 | 286T0723 | | | IRS-C,SHELF TO SEL PNL (continued) | | | | | | | | | | | |
| 020 | 24 | | PK | | 6-8 | 21-58-11 | D00743 | 20 | | | TB0066Y | A022 | BJ | | ALL |
| 021 | 24 | | PK | | 6-8 | 21-58-11 | D00743 | 19 | | | TB0066Z | 23 | BJ | | ALL |
| 022 | 20 | | PA | | 6-0 | 33-13-16 | D00743 | 2 | | | GD00092 | A.. | 2 | | ALL |
| 023 | 20 | | PA | | 6-8 | 33-13-16 | D00743 | 1 | | | TB0068H | 1 | 2 | | ALL |
| 028 | 22 | | PA | | 23-0 | 33-16-17 | D04757J | 8 | | | TB0031F | A025 | 2 | | ALL |
| 201 | 20 | | UA | | 1-6 | 34-21-31 | D00743 | REF | | IA | GD00707 | S.. | E | | ALL |
| 201B | 24 | | PW | IA | 39-3 | 34-21-31 | D04757J | 20 | | | D00743 | 27 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-21-31 | D04757J | 19 | | | D00743 | 26 | | | ALL |
| 201Z | | | | IA | 0-0 | 34-21-31 | D04757J | 21 | | | D00743 | REF | | IA | ALL |
| 202 | 20 | | UA | | 1-6 | 34-21-31 | D00743 | REF | | IB | GD00707 | S.. | E | | ALL |
| 202B | 24 | | PW | IB | 39-3 | 34-21-31 | D04757J | 23 | | | D00743 | 25 | | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-21-31 | D04757J | 24 | | | D00743 | 24 | | | ALL |
| 202Z | | | | IB | 0-0 | 34-21-31 | D04757J | 22 | | | D00743 | REF | | IB | ALL |
| W0724 | 286T0724 | | | LEFT AFT OXYGEN LATCHES | | | | | | | | | | | |
| 001 | 16 | | PA | | 10-8 | 35-21-12 | D05736P | 1 | | | SM00002 | | S | | 050-099 |
| 001 | 14 | | PA | | 32-11 | 35-21-12 | D06644P | 1 | FN | | SM00001 | | S | | 150-199 |
| 001 | 14 | | PA | | 42-7 | 35-21-12 | D06644P | 1 | FN | | SM00002 | | S | | 275-299 |
| 002 | 14 | | PA | | 2-7 | 35-21-12 | SM00002 | | | S | SM00001 | | S | | 150-199 |
| 003 | 20 | | PA | | 1-11 | 35-21-12 | D01114 | 1 | | | SM00002 | | S | | 275-299 |
| 004 | 20 | | PA | | 3-8 | 35-21-12 | D01114 | 2 | | | GD05018 | D.. | E | | 275-299 |
| 005 | 16 | | PA | | 4-3 | 35-21-12 | SM00002 | | | S | SM00004 | | S | | 050-099 |
| 005 | 14 | | PA | | 3-9 | 35-21-12 | SM00002 | | | S | SM00004 | | S | | 150-199 |
| 005 | 14 | | PA | | 7-1 | 35-21-12 | SM00002 | | | S | SM00004 | | S | | 275-299 |
| 006 | 20 | | PA | | 10-10 | 35-21-12 | SM00002 | | | S | D01116 | 1 | | | 050-099 |
| 006 | 20 | | PA | | 1-7 | 35-21-12 | SM00002 | | | S | D01116 | 1 | | | 150-199 |
| 006 | 20 | | PA | | 3-1 | 35-21-12 | SM00002 | | | S | D01116 | 1 | | | 275-299 |
| 007 | 20 | | PA | | 11-4 | 35-21-12 | GD02554 | | D.. | E | D01116 | 2 | | | 050-099 |
| 007 | 20 | | PA | | 4-2 | 35-21-12 | GD05022 | | D.. | E | D01116 | 2 | | | 150-199 |
| 007 | 20 | | PA | | 4-0 | 35-21-12 | GD05022 | | D.. | E | D01116 | 2 | | | 275-299 |
| 009 | 20 | | PA | | 3-3 | 35-21-12 | SM00004 | | | S | D01118 | 1 | | | 050-099 |
| 009 | 20 | | PA | | 1-8 | 35-21-12 | SM00004 | | | S | D01118 | 1 | | | 150-199 |
| 009 | 20 | | PA | | 3-0 | 35-21-12 | SM00004 | | | S | D01118 | 1 | | | 275-299 |
| 010 | 20 | | PA | | 9-9 | 35-21-12 | GD02554 | | D.. | E | D01118 | 2 | | | 050-099 |
| 010 | 20 | | PA | | 1-10 | 35-21-12 | GD05022 | | D.. | E | D01118 | 2 | | | 150-199 |
| 010 | 20 | | PA | | 1-8 | 35-21-12 | GD05022 | | D.. | E | D01118 | 2 | | | 275-299 |
| 011 | 20 | | PA | | 1-7 | 35-21-12 | SM00004 | | | S | D01120 | 1 | | | 050-099 |
| 011 | 20 | | PA | | 3-0 | 35-21-12 | SM00004 | | | S | D01120 | 1 | | | 150-199 |
| 011 | 20 | | PA | | 1-9 | 35-21-12 | SM00004 | | | S | D01120 | 1 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 6

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0724 | 286T0724 | | | LEFT AFT OXYGEN LATCHES (continued) | | | | | | | | | | | | |
| 012 | 20 | | PA | 4-3 | 35-21-12 | GD01792 | D.. | E | | D01120 | 2 | | | 050-099 | | |
| 012 | 20 | | PA | 3-10 | 35-21-12 | GD05022 | D.. | E | | D01120 | 2 | | | 150-199 | | |
| 012 | 20 | | PA | 3-11 | 35-21-12 | GD05022 | D.. | E | | D01120 | 2 | | | 275-299 | | |
| 013 | 16 | | PA | 5-4 | 35-21-12 | SM00006 | | S | | SM00004 | | | S | 050-099 | | |
| 013 | 14 | | PA | 5-3 | 35-21-12 | SM00006 | | S | | SM00004 | | | S | 150-199 | | |
| 013 | 14 | | PA | 5-4 | 35-21-12 | SM00006 | | S | | SM00004 | | | S | 275-299 | | |
| 014 | 20 | | PA | 3-0 | 35-21-12 | SM00006 | | S | | D01018 | 1 | | | 050-099 | | |
| 014 | 20 | | PA | 1-5 | 35-21-12 | SM00006 | | S | | D01018 | 1 | | | 150-199 | | |
| 014 | 20 | | PA | 2-8 | 35-21-12 | SM00006 | | S | | D01018 | 1 | | | 275-299 | | |
| 015 | 20 | | PA | 1-8 | 35-21-12 | GD01792 | D.. | E | | D01018 | 2 | | | 050-099 | | |
| 015 | 20 | | PA | 4-6 | 35-21-12 | GD05026 | D.. | E | | D01018 | 2 | | | 150-199 | | |
| 015 | 20 | | PA | 4-3 | 35-21-12 | GD05026 | D.. | E | | D01018 | 2 | | | 275-299 | | |
| 017 | 20 | | PA | 1-8 | 35-21-12 | SM00006 | | S | | D01020 | 1 | | | 050-099 | | |
| 017 | 20 | | PA | 3-7 | 35-21-12 | SM00006 | | S | | D01020 | 1 | | | 150-199 | | |
| 017 | 20 | | PA | 2-3 | 35-21-12 | SM00006 | | S | | D01020 | 1 | | | 275-299 | | |
| 018 | 20 | | PA | 4-0 | 35-21-12 | GD01792 | D.. | E | | D01020 | 2 | | | 050-099 | | |
| 018 | 20 | | PA | 1-11 | 35-21-12 | GD05026 | D.. | E | | D01020 | 2 | | | 150-199 | | |
| 018 | 20 | | PA | 1-7 | 35-21-12 | GD05026 | D.. | E | | D01020 | 2 | | | 275-299 | | |
| 019 | 16 | | PA | 5-5 | 35-21-12 | SM00008 | | S | | SM00006 | | | S | 050-099 | | |
| 019 | 14 | | PA | 6-9 | 35-21-12 | SM00008 | | S | | SM00022 | | | S | 150-199 | | |
| 019 | 14 | | PA | 5-3 | 35-21-12 | SM00008 | | S | | SM00022 | | | S | 275-299 | | |
| 020 | 20 | | PA | 3-2 | 35-21-12 | SM00008 | | S | | D01022 | 1 | | | 050-099 | | |
| 020 | 20 | | PA | 2-7 | 35-21-12 | SM00008 | | S | | D01022 | 1 | | | 150-199 | | |
| 020 | 20 | | PA | 1-6 | 35-21-12 | SM00008 | | S | | D01022 | 1 | | | 275-299 | | |
| 021 | 20 | | PA | 4-5 | 35-21-12 | GD01798 | D.. | E | | D01022 | 2 | | | 050-099 | | |
| 021 | 20 | | PA | 4-6 | 35-21-12 | GD05034 | D.. | E | | D01022 | 2 | | | 150-199 | | |
| 021 | 20 | | PA | 4-2 | 35-21-12 | GD05034 | D.. | E | | D01022 | 2 | | | 275-299 | | |
| 023 | 20 | | PA | 1-8 | 35-21-12 | SM00008 | | S | | D01024 | 1 | | | 050-099 | | |
| 023 | 20 | | PA | 2-3 | 35-21-12 | SM00008 | | S | | D01024 | 1 | | | 150-199 | | |
| 023 | 20 | | PA | 3-2 | 35-21-12 | SM00008 | | S | | D01024 | 1 | | | 275-299 | | |
| 024 | 20 | | PA | 1-9 | 35-21-12 | GD01798 | D.. | E | | D01024 | 2 | | | 050-099 | | |
| 024 | 20 | | PA | 2-0 | 35-21-12 | GD05034 | D.. | E | | D01024 | 2 | | | 150-199 | | |
| 024 | 20 | | PA | 1-9 | 35-21-12 | GD05034 | D.. | E | | D01024 | 2 | | | 275-299 | | |
| 025 | 16 | | PA | 6-3 | 35-21-12 | SM00010 | | S | | SM00008 | | | S | 050-099 | | |
| 025 | 14 | | PA | 6-2 | 35-21-12 | SM00010 | | S | | SM00008 | | | S | 150-199 | | |
| 025 | 14 | | PA | 6-5 | 35-21-12 | SM00010 | | S | | SM00008 | | | S | 275-299 | | |
| 027 | 20 | | PA | 3-3 | 35-21-12 | SM00010 | | S | | D01026 | 1 | | | 050-099 | | |
| 027 | 20 | | PA | 3-1 | 35-21-12 | SM00010 | | S | | D01026 | 1 | | | 150-199 | | |
| 027 | 20 | | PA | 2-2 | 35-21-12 | SM00010 | | S | | D01026 | 1 | | | 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0724 | 286T0724 | | | LEFT AFT OXYGEN LATCHES (continued) | | | | | | | | | | | |
| 028 | 20 | | PA | 3-10 | 35-21-12 | GD01798 | D.. | E | | D01026 | | | 2 | | 050-099 |
| 028 | 20 | | PA | 4-0 | 35-21-12 | GD05034 | D.. | E | | D01026 | | | 2 | | 150-199 |
| 028 | 20 | | PA | 3-9 | 35-21-12 | GD05034 | D.. | E | | D01026 | | | 2 | | 275-299 |
| 029 | 16 | | PA | 5-4 | 35-21-12 | SM00010 | | S | | SM00012 | | | | S | 050-099 |
| 029 | 14 | | PA | 5-4 | 35-21-12 | SM00010 | | S | | SM00012 | | | | S | 150-199 |
| 029 | 14 | | PA | 5-5 | 35-21-12 | SM00010 | | S | | SM00012 | | | | S | 275-299 |
| 030 | 20 | | PA | 1-6 | 35-21-12 | SM00010 | | S | | D01028 | | | 1 | | 050-099 |
| 030 | 20 | | PA | 2-1 | 35-21-12 | SM00010 | | S | | D01028 | | | 1 | | 150-199 |
| 030 | 20 | | PA | 2-9 | 35-21-12 | SM00010 | | S | | D01028 | | | 1 | | 275-299 |
| 031 | 20 | | PA | 4-3 | 35-21-12 | GD01804 | D.. | E | | D01028 | | | 2 | | 050-099 |
| 031 | 20 | | PA | 4-4 | 35-21-12 | GD01804 | D.. | E | | D01028 | | | 2 | | 150-199 |
| 031 | 20 | | PA | 4-2 | 35-21-12 | GD01804 | D.. | E | | D01028 | | | 2 | | 275-299 |
| 033 | 20 | | PA | 3-2 | 35-21-12 | SM00012 | | S | | D01030 | | | 1 | | 050-099 |
| 033 | 20 | | PA | 2-8 | 35-21-12 | SM00012 | | S | | D01030 | | | 1 | | 150-199 |
| 033 | 20 | | PA | 1-11 | 35-21-12 | SM00012 | | S | | D01030 | | | 1 | | 275-299 |
| 034 | 20 | | PA | 1-9 | 35-21-12 | GD01804 | D.. | E | | D01030 | | | 2 | | 050-099 |
| 034 | 20 | | PA | 1-11 | 35-21-12 | GD01804 | D.. | E | | D01030 | | | 2 | | 150-199 |
| 034 | 20 | | PA | 1-7 | 35-21-12 | GD01804 | D.. | E | | D01030 | | | 2 | | 275-299 |
| 035 | 20 | | PA | 1-7 | 35-21-12 | SM00012 | | S | | D01032 | | | 1 | | 050-099 |
| 035 | 20 | | PA | 1-9 | 35-21-12 | SM00012 | | S | | D01032 | | | 1 | | 150-199 |
| 035 | 20 | | PA | 2-5 | 35-21-12 | SM00012 | | S | | D01032 | | | 1 | | 275-299 |
| 036 | 20 | | PA | 3-10 | 35-21-12 | GD01804 | D.. | E | | D01032 | | | 2 | | 050-099 |
| 036 | 20 | | PA | 3-11 | 35-21-12 | GD01804 | D.. | E | | D01032 | | | 2 | | 150-199 |
| 036 | 20 | | PA | 3-8 | 35-21-12 | GD01804 | D.. | E | | D01032 | | | 2 | | 275-299 |
| 037 | 16 | | PA | 4-10 | 35-21-12 | SM00014 | | S | | SM00012 | | | | S | 050-099 |
| 037 | 14 | | PA | 5-3 | 35-21-12 | SM00014 | | S | | SM00012 | | | | S | 150-199 |
| 037 | 14 | | PA | 3-3 | 35-21-12 | SM00014 | | S | | SM00012 | | | | S | 275-299 |
| 038 | 20 | | PA | 2-9 | 35-21-12 | SM00014 | | S | | D01034 | | | 1 | | 050-099 |
| 038 | 20 | | PA | 2-10 | 35-21-12 | SM00014 | | S | | D01034 | | | 1 | | 150-199 |
| 038 | 20 | | PA | 2-2 | 35-21-12 | SM00014 | | S | | D01034 | | | 1 | | 275-299 |
| 039 | 20 | | PA | 4-2 | 35-21-12 | GD01810 | D.. | E | | D01034 | | | 2 | | 050-099, 150-199 |
| 039 | 20 | | PA | 4-1 | 35-21-12 | GD01810 | D.. | E | | D01034 | | | 2 | | 275-299 |
| 041 | 20 | | PA | 2-5 | 35-21-12 | SM00014 | | S | | D01036 | | | 1 | | 050-099 |
| 041 | 20 | | PA | 2-2 | 35-21-12 | SM00014 | | S | | D01036 | | | 1 | | 150-199 |
| 041 | 20 | | PA | 4-9 | 35-21-12 | SM00014 | | S | | D01036 | | | 1 | | 275-299 |
| 042 | 20 | | PA | 1-9 | 35-21-12 | GD01810 | D.. | E | | D01036 | | | 2 | | 050-099 |
| 042 | 20 | | PA | 1-10 | 35-21-12 | GD01810 | D.. | E | | D01036 | | | 2 | | 150-199 |
| 042 | 20 | | PA | 1-8 | 35-21-12 | GD01810 | D.. | E | | D01036 | | | 2 | | 275-299 |
| 043 | 16 | | PA | 5-3 | 35-21-12 | SM00016 | | S | | SM00014 | | | | S | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|-----|---|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0724 | 286T0724 | | | LEFT AFT OXYGEN LATCHES (continued) | | | | | | | | | | | | | | |
| 043 | 14 | | PA | 20-0 | 35-21-12 | SM00016 | | | | | | | S | SM00014 | | | S | 150-199 |
| 043 | 14 | | PA | 6-2 | 35-21-12 | SM00016 | | | | | | | S | SM00014 | | | S | 275-299 |
| 044 | 20 | | PA | 3-11 | 35-21-12 | SM00014 | | | | | | | S | D01038 | 1 | | | 050-099 |
| 044 | 20 | | PA | 3-4 | 35-21-12 | SM00014 | | | | | | | S | D01038 | 1 | | | 150-199 |
| 044 | 20 | | PA | 6-5 | 35-21-12 | SM00014 | | | | | | | S | D01038 | 1 | | | 275-299 |
| 045 | 20 | | PA | 3-2 | 35-21-12 | GD01810 | | | | | D.. | | E | D01038 | 2 | | | 050-099 |
| 045 | 20 | | PA | 3-0 | 35-21-12 | GD01810 | | | | | D.. | | E | D01038 | 2 | | | 150-199 |
| 045 | 20 | | PA | 2-10 | 35-21-12 | GD01810 | | | | | D.. | | E | D01038 | 2 | | | 275-299 |
| 047 | 20 | | PA | 11-4 | 35-21-12 | SM00016 | | | | | | | S | D03834 | 1 | | | 050-099 |
| 047 | 20 | | PA | 7-7 | 35-21-12 | SM00016 | | | | | | | S | D03834 | 1 | | | 150-199 |
| 047 | 20 | | PA | 13-9 | 35-21-12 | SM00016 | | | | | | | S | D03834 | 1 | | | 275-299 |
| 048 | 20 | | PA | 3-7 | 35-21-12 | GD00026 | | | | | D.. | 2 | | D03834 | 2 | | | 050-099 |
| 048 | 20 | | PA | 5-2 | 35-21-12 | GD00026 | | | | | D.. | 2 | | D03834 | 2 | | | 150-199 |
| 048 | 20 | | PA | 3-8 | 35-21-12 | GD00026 | | | | | D.. | 2 | | D03834 | 2 | | | 275-299 |
| 049 | 20 | | PA | 14-5 | 35-21-12 | D10548 | | | | | | 2 | | GD01126 | | D.. | 2 | 150-199 |
| 050 | 20 | | PA | 4-10 | 35-21-12 | D01040 | | | | | | 1 | | SM00016 | | | S | 150-199 |
| 050 | 20 | | PA | 21-7 | 35-21-12 | D01040 | | | | | | 1 | | SM00016 | | | S | 275-299 |
| 051 | 20 | | PA | 14-0 | 35-21-12 | D01040 | | | | | | 2 | | GD00026 | | D.. | 2 | 150-199 |
| 051 | 20 | | PA | 14-6 | 35-21-12 | D01040 | | | | | | 2 | | GD00026 | | D.. | 2 | 275-299 |
| 055 | 20 | | PA | 18-2 | 35-21-12 | D10020 | | | | | | 1 | | SM00016 | | | S | 050-099 |
| 056 | 20 | | PA | 10-2 | 35-21-12 | D10020 | | | | | | 2 | | GD00932 | | D.. | 2 | 050-099 |
| 058 | 20 | | PA | 4-9 | 35-21-12 | SM00016 | | | | | | | S | D10548 | 1 | | | 150-199 |
| 060 | 14 | | PA | 6-6 | 35-21-12 | SM00006 | | | | | | | S | SM00020 | | | S | 150-199 |
| 060 | 14 | | PA | 4-5 | 35-21-12 | SM00006 | | | | | | | S | SM00020 | | | S | 275-299 |
| 062 | 14 | | PA | 5-3 | 35-21-12 | SM00020 | | | | | | | S | SM00022 | | | S | 150-199 |
| 062 | 14 | | PA | 5-5 | 35-21-12 | SM00020 | | | | | | | S | SM00022 | | | S | 275-299 |
| 064 | 20 | | PA | 2-4 | 35-21-12 | SM00020 | | | | | | | S | D11256 | 1 | | | 150-199 |
| 064 | 20 | | PA | 2-1 | 35-21-12 | SM00020 | | | | | | | S | D11256 | 1 | | | 275-299 |
| 065 | 20 | | PA | 3-10 | 35-21-12 | GD05026 | | | | | D.. | | E | D11256 | 2 | | | 150-199 |
| 065 | 20 | | PA | 3-6 | 35-21-12 | GD05026 | | | | | D.. | | E | D11256 | 2 | | | 275-299 |
| 066 | 20 | | PA | 3-0 | 35-21-12 | SM00020 | | | | | | | S | D11258 | 1 | | | 150-199 |
| 066 | 20 | | PA | 3-2 | 35-21-12 | SM00020 | | | | | | | S | D11258 | 1 | | | 275-299 |
| 067 | 20 | | PA | 4-3 | 35-21-12 | GD05030 | | | | | D.. | | E | D11258 | 2 | | | 150-199 |
| 067 | 20 | | PA | 4-2 | 35-21-12 | GD05030 | | | | | D.. | | E | D11258 | 2 | | | 275-299 |
| 068 | 20 | | PA | 1-9 | 35-21-12 | SM00022 | | | | | | | S | D11260 | 1 | | | 150-199 |
| 068 | 20 | | PA | 1-7 | 35-21-12 | SM00022 | | | | | | | S | D11260 | 1 | | | 275-299 |
| 069 | 20 | | PA | 1-10 | 35-21-12 | GD05030 | | | | | D.. | | E | D11260 | 2 | | | 150-199 |
| 069 | 20 | | PA | 1-8 | 35-21-12 | GD05030 | | | | | D.. | | E | D11260 | 2 | | | 275-299 |
| 070 | 20 | | PA | 2-10 | 35-21-12 | SM00022 | | | | | | | S | D11262 | 1 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0724 | 286T0724 | | | LEFT AFT OXYGEN LATCHES (continued) | | | | | | | | | | | |
| 070 | 20 | | PA | | 3-0 | 35-21-12 | SM00022 | | S | | D11262 | | 1 | | 275-299 |
| 071 | 20 | | PA | | 3-10 | 35-21-12 | GD05030 | D.. | E | | D11262 | | 2 | | 150-199, 275-299 |
| 072 | 14 | | PA | | 3-6 | 35-21-12 | D06644P | 2 | FN | | SM00023 | | | S | 275-299 |
| 073 | 20 | | PA | | 2-10 | 35-21-12 | SM00023 | | S | | D01150 | | 1 | | 275-278 |
| 073 | 20 | | PA | | 4-0 | 35-21-12 | SM00023 | | S | | D01150 | | 1 | | 280-299 |
| 074 | 20 | | PA | | 4-3 | 35-21-12 | D01150 | 2 | | | GD05006 | D.. | E | | 275-278 |
| 074 | 20 | | PA | | 6-0 | 35-21-12 | D01150 | 2 | | | GD05006 | D.. | E | | 280-299 |
| 075 | 14 | | PA | | 4-6 | 35-21-12 | SM00023 | | S | | SM00024 | | | S | 275-299 |
| 076 | 20 | | PA | | 2-0 | 35-21-12 | SM00023 | | S | | D01152 | | 1 | | 275-299 |
| 077 | 20 | | PA | | 1-10 | 35-21-12 | D01152 | 2 | | | GD05006 | D.. | E | | 275-299 |
| 078 | 20 | | PA | | 2-2 | 35-21-12 | SM00024 | | S | | D01154 | | 1 | | 275-299 |
| 079 | 20 | | PA | | 3-11 | 35-21-12 | D01154 | 2 | | | GD05006 | D.. | E | | 275-299 |
| 080 | 14 | | PA | | 5-2 | 35-21-12 | D06644P | 2 | FN | | SM00025 | | | S | 150-199 |
| 080 | 14 | | PA | | 2-5 | 35-21-12 | SM00024 | | S | | SM00025 | | | S | 275-299 |
| 081 | 20 | | PA | | 4-7 | 35-21-12 | SM00025 | | S | | D11254 | | 1 | | 150-199 |
| 081 | 20 | | PA | | 2-10 | 35-21-12 | SM00024 | | S | | D11254 | | 1 | | 275-299 |
| 082 | 20 | | PA | | 4-4 | 35-21-12 | D11254 | 2 | | | GD05314 | D.. | E | | 150-199 |
| 082 | 20 | | PA | | 3-2 | 35-21-12 | D11254 | 2 | | | GD05010 | D.. | E | | 275-299 |
| 083 | 20 | | PA | | 2-1 | 35-21-12 | SM00025 | | S | | D01156 | | 1 | | 150-199 |
| 083 | 20 | | PA | | 3-0 | 35-21-12 | SM00025 | | S | | D01156 | | 1 | | 275-299 |
| 084 | 20 | | PA | | 1-10 | 35-21-12 | D01156 | 2 | | | GD05314 | D.. | E | | 150-199 |
| 084 | 20 | | PA | | 2-2 | 35-21-12 | D01156 | 2 | | | GD05010 | D.. | E | | 275-299 |
| 085 | 14 | | PA | | 3-4 | 35-21-12 | SM00025 | | S | | SM00026 | | | S | 150-199 |
| 085 | 14 | | PA | | 18-7 | 35-21-12 | SM00025 | | S | | SM00026 | | | S | 275-299 |
| 088 | 20 | | PA | | 2-5 | 35-21-12 | SM00026 | | S | | D01158 | | 1 | | 150-199 |
| 088 | 20 | | PA | | 10-6 | 35-21-12 | SM00026 | | S | | D01160 | | 1 | | 275-278 |
| 088 | 20 | | PA | | 11-0 | 35-21-12 | SM00026 | | S | | D01160 | | 1 | | 280-299 |
| 089 | 20 | | PA | | 4-1 | 35-21-12 | D01158 | 2 | | | GD05314 | D.. | E | | 150-199 |
| 089 | 20 | | PA | | 3-4 | 35-21-12 | D01160 | 2 | | | GD00683 | D.. | E | | 275-278 |
| 089 | 20 | | PA | | 3-10 | 35-21-12 | D01160 | 2 | | | GD00683 | D.. | E | | 280-299 |
| 090 | 14 | | PA | | 6-2 | 35-21-12 | SM00026 | | S | | SM00027 | | | S | 150-199 |
| 090 | 14 | | PA | | 6-0 | 35-21-12 | SM00026 | | S | | SM00027 | | | S | 275-299 |
| 091 | 20 | | PA | | 2-4 | 35-21-12 | SM00026 | | S | | D01180 | | 1 | | 150-199 |
| 091 | 20 | | PA | | 8-3 | 35-21-12 | SM00026 | | S | | D01180 | | 1 | | 275-299 |
| 092 | 20 | | PA | | 4-10 | 35-21-12 | D01180 | 2 | | | GD05136 | D.. | E | | 150-199 |
| 092 | 20 | | PA | | 2-7 | 35-21-12 | D01180 | 2 | | | GD05480 | D.. | E | | 275-299 |
| 093 | 20 | | PA | | 2-8 | 35-21-12 | SM00027 | | S | | D01182 | | 1 | | 150-199 |
| 093 | 20 | | PA | | 2-10 | 35-21-12 | SM00027 | | S | | D01182 | | 1 | | 275-299 |
| 094 | 20 | | PA | | 2-4 | 35-21-12 | D01182 | 2 | | | GD05136 | D.. | E | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|--|-------|-------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0724 | 286T0724 | LEFT AFT OXYGEN LATCHES (continued) | | | | | | | | | | | | | | | |
| 094 | 20 | PA | | 4-3 | 35-21-12 | D01182 | | 2 | | | | | GD05014 | D.. | E | | 275-299 |
| 095 | 14 | PA | | 17-3 | 35-21-12 | SM00027 | | | S | | | | SM00028 | | S | | 150-199 |
| 095 | 14 | PA | | 4-5 | 35-21-12 | SM00027 | | | S | | | | SM00028 | | S | | 275-299 |
| 096 | 20 | PA | | 2-4 | 35-21-12 | SM00027 | | | S | | | | D01184 | | 1 | | 150-199 |
| 096 | 20 | PA | | 1-10 | 35-21-12 | SM00027 | | | S | | | | D01184 | | 1 | | 275-299 |
| 097 | 20 | PA | | 3-8 | 35-21-12 | D01184 | | 2 | | | | | GD05136 | D.. | E | | 150-199 |
| 097 | 20 | PA | | 1-10 | 35-21-12 | D01184 | | 2 | | | | | GD05014 | D.. | E | | 275-299 |
| 098 | 20 | PA | | 11-11 | 35-21-12 | SM00028 | | | S | | | | D01186 | | 1 | | 150-199 |
| 098 | 20 | PA | | 1-11 | 35-21-12 | SM00028 | | | S | | | | D01186 | | 1 | | 275-299 |
| 099 | 20 | PA | | 3-0 | 35-21-12 | D01186 | | 2 | | | | | GD04990 | D.. | E | | 150-199 |
| 099 | 20 | PA | | 3-10 | 35-21-12 | D01186 | | 2 | | | | | GD05014 | D.. | E | | 275-299 |
| 100 | 20 | PA | | 3-2 | 35-21-12 | SM00028 | | | S | | | | D01188 | | 1 | | 275-299 |
| 101 | 20 | PA | | 4-2 | 35-21-12 | D01188 | | 2 | | | | | GD05018 | D.. | E | | 275-299 |
| 102 | 20 | PA | | 1-9 | 35-21-12 | SM00028 | | | S | | | | D01190 | | 1 | | 150-199 |
| 102 | 20 | PA | | 6-2 | 35-21-12 | SM00028 | | | S | | | | D01190 | | 1 | | 275-299 |
| 103 | 20 | PA | | 1-10 | 35-21-12 | D01190 | | 2 | | | | | GD05018 | D.. | E | | 150-199 |
| 103 | 20 | PA | | 1-8 | 35-21-12 | D01190 | | 2 | | | | | GD05018 | D.. | E | | 275-299 |
| 105 | 20 | PA | | 2-3 | 35-21-12 | D13536 | | 1 | | | | | SM00001 | | S | | 150-199 |
| 106 | 20 | PA | | 3-1 | 35-21-12 | D13536 | | 2 | | | | | GD05644 | D.. | E | | 150-199 |
| 107 | 20 | PA | | 2-4 | 35-21-12 | D13538 | | 1 | | | | | SM00001 | | S | | 150-199 |
| 108 | 20 | PA | | 2-7 | 35-21-12 | D13538 | | 2 | | | | | GD05644 | D.. | E | | 150-199 |
| 109 | 20 | PA | | 18-1 | 35-21-12 | D12024 | | 1 | | | | | SM00016 | | S | | 050-099 |
| 109 | 20 | PA | | 19-6 | 35-21-12 | D12024 | | 1 | | | | | SM00016 | | S | | 150-199 |
| 110 | 20 | PA | | 22-2 | 35-21-12 | D12024 | | 2 | | | | | GD01810 | D.. | E | | 050-099 |
| 110 | 20 | PA | | 5-2 | 35-21-12 | D12024 | | 2 | | | | | GD01810 | D.. | E | | 150-199 |
| W0725 | 286T0725 | IRS-R,SHELF TO SEL PNL | | | | | | | | | | | | | | | |
| 003 | 20 | PA | | 42-0 | 34-21-21 | D04761J | | 3 | | | | | D00741 | | 3 | | ALL |
| 004 | 20 | PA | | 42-0 | 34-21-21 | D04761J | | 4 | | | | | D00741 | | 4 | | ALL |
| 005 | 20 | PA | | 42-0 | 34-21-21 | D04761J | | 5 | | | | | D00741 | | 5 | | ALL |
| 008 | 20 | PA | | 1-6 | 34-21-21 | GD00633 | | S.. | E | | | | D00741 | | 8 | | ALL |
| 010 | 22 | PA | | 7-0 | 33-16-17 | TB0066Y | | C036 | BJ | | | | D00741 | | 10 | | 050-099, 155-199 |
| 010 | 22 | PQ | AJ | 7-0 | 33-16-17 | TB0068Y | | C018 | BJ | | | | D00741 | | 10 | | 150-154, 275-299 |
| 010Z | | | AJ | 0-0 | 33-16-17 | TB0068Y | | DED | | | | | D00741 | DED | | | 150-154, 275-299 |
| 012 | 24 | PK | | 42-0 | 34-21-21 | D04761J | | 12 | | | | | D00741 | | 12 | | ALL |
| 013 | 24 | PK | | 42-0 | 34-21-21 | D04761J | | 13 | | | | | D00741 | | 13 | | ALL |
| 014 | 22 | PA | | 42-0 | 34-21-21 | D04761J | | 14 | | | | | D00741 | | 14 | | ALL |
| 015 | 22 | PA | | 42-0 | 34-21-21 | D04761J | | 15 | | | | | D00741 | | 15 | | ALL |
| 016 | 22 | PA | | 42-0 | 34-21-21 | D04761J | | 16 | | | | | D00741 | | 16 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0725 | 286T0725 | | | IRS-R,SHELF TO SEL PNL (continued) | | | | | | | | | | | |
| 017 | 22 | | PA | | 42-0 | 34-21-21 | D04761J | 17 | | | D00741 | 17 | | | ALL |
| 018 | 22 | | PA | | 6-0 | 33-16-17 | TB0066Y | A036 | BJ | | D00741 | 18 | | | ALL |
| 019 | 22 | | PA | | 7-0 | 33-16-17 | TB0066Y | C036 | BJ | | D00741 | 11 | | | 050-099, 155-199 |
| 019 | 22 | | PQ | AS | 7-0 | 33-16-17 | TB0068Y | C018 | BJ | | D00741 | 11 | | | 150-154, 275-299 |
| 019Z | | | | AS | 0-0 | 33-16-17 | TB0068Y | DED | | | D00741 | DED | | | 150-154, 275-299 |
| 020 | 24 | | PK | | 7-0 | 21-58-11 | D00741 | 20 | | | TB0066Y | A022 | BJ | | ALL |
| 021 | 24 | | PK | | 7-0 | 21-58-11 | D00741 | 19 | | | TB0066Z | 23 | BJ | | ALL |
| 022 | 20 | | PA | | 6-0 | 33-13-16 | D00741 | 2 | | | GD00263 | A.. | 2 | | ALL |
| 023 | 20 | | PA | | 7-0 | 33-13-16 | D00741 | 1 | | | TB0068H | 1 | 2 | | ALL |
| 028 | 22 | | PA | | 24-0 | 33-16-17 | D04761J | 8 | | | TB0031F | C025 | 2 | | ALL |
| 201 | 20 | | UA | | 1-6 | 34-21-21 | D00741 | REF | | FA | GD00633 | S.. | E | | ALL |
| 201B | 24 | | PW | IA | 42-0 | 34-21-21 | D04761J | 20 | | | D00741 | 27 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-21-21 | D04761J | 19 | | | D00741 | 26 | | | ALL |
| 201Z | | | | IA | 0-0 | 34-21-21 | D04761J | 21 | | | D00741 | REF | | FA | ALL |
| 202 | 20 | | UA | | 1-6 | 34-21-21 | D00741 | REF | | FB | GD00633 | S.. | E | | ALL |
| 202B | 24 | | PW | IB | 42-0 | 34-21-21 | D04761J | 23 | | | D00741 | 25 | | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-21-21 | D04761J | 24 | | | D00741 | 24 | | | ALL |
| 202Z | | | | IB | 0-0 | 34-21-21 | D04761J | 22 | | | D00741 | REF | | FB | ALL |
| W0726 | 286T0726 | | | CENTER AFT OXYGEN LATCHES | | | | | | | | | | | |
| 001 | 16 | | PA | | 15-0 | 35-21-14 | D05730P | 1 | | | D06000P | 1 | | | 050-099 |
| W0728 | 286T0728 | | | R OXYGEN MASK DEPLOYMENT | | | | | | | | | | | |
| 001 | 16 | | PA | | 14-0 | 35-21-13 | D05728P | 1 | | | SM00002 | | S | | 050-099 |
| 001 | 14 | | PA | | 34-0 | 35-21-13 | D06646P | 1 | FN | | SM00001 | | S | | 150-199 |
| 001 | 14 | | PA | | 43-0 | 35-21-13 | D06646P | 1 | FN | | SM00002 | | S | | 275-299 |
| 002 | 14 | | PA | | 2-0 | 35-21-13 | SM00001 | | | | SM00002 | | S | | 150-199 |
| 003 | 20 | | PA | | 3-0 | 35-21-13 | SM00002 | | | | D03016 | 1 | | | 275-299 |
| 004 | 20 | | PA | | 5-0 | 35-21-13 | GD05058 | D.. | E | | D03016 | 2 | | | 275-278 |
| 004 | 20 | | PA | | 6-0 | 35-21-13 | GD05058 | D.. | E | | D03016 | 2 | | | 280-299 |
| 005 | 16 | | PA | | 5-0 | 35-21-13 | SM00002 | | | | SM00004 | | S | | 050-099 |
| 005 | 14 | | PA | | 6-0 | 35-21-13 | SM00002 | | | | SM00004 | | S | | 150-199 |
| 005 | 14 | | PA | | 8-0 | 35-21-13 | SM00002 | | | | SM00004 | | S | | 275-299 |
| 006 | 20 | | PA | | 11-0 | 35-21-13 | SM00002 | | | | D03018 | 1 | | | 050-099 |
| 006 | 20 | | PA | | 4-0 | 35-21-13 | SM00002 | | | | D03018 | 1 | | | 150-199, 275-278 |
| 006 | 20 | | PA | | 5-0 | 35-21-13 | SM00002 | | | | D03018 | 1 | | | 280-299 |
| 007 | 20 | | PA | | 7-0 | 35-21-13 | GD02504 | D.. | E | | D03018 | 2 | | | 050-099 |
| 007 | 20 | | PA | | 5-0 | 35-21-13 | GD05062 | D.. | E | | D03018 | 2 | | | 150-199, 275-299 |
| 009 | 20 | | PA | | 4-0 | 35-21-13 | SM00004 | | | | D03020 | 1 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0728 | 286T0728 | | | R OXYGEN MASK DEPLOYMENT (continued) | | | | | | | | | | | | | |
| 009 | 20 | | PA | 5-0 | 35-21-13 | SM00004 | | | | | | | D03020 | 1 | | | 275-299 |
| 010 | 20 | | PA | 5-0 | 35-21-13 | GD02504 | | D.. | E | | | | D03020 | 2 | | | 050-099 |
| 010 | 20 | | PA | 3-0 | 35-21-13 | GD05062 | | D.. | E | | | | D03020 | 2 | | | 150-199, 275-299 |
| 011 | 20 | | PA | 4-0 | 35-21-13 | SM00004 | | | | | | | D03022 | 1 | | | 050-099, 150-199 |
| 011 | 20 | | PA | 3-0 | 35-21-13 | SM00004 | | | | | | | D03022 | 1 | | | 275-299 |
| 012 | 20 | | PA | 5-0 | 35-21-13 | GD01714 | | D.. | E | | | | D03022 | 2 | | | 050-099 |
| 012 | 20 | | PA | 5-0 | 35-21-13 | GD05062 | | D.. | E | | | | D03022 | 2 | | | 150-199, 275-299 |
| 013 | 16 | | PA | 6-0 | 35-21-13 | SM00004 | | | | | | | SM00006 | | S | | 050-099 |
| 013 | 14 | | PA | 6-0 | 35-21-13 | SM00004 | | | | | | | SM00006 | | S | | 150-199, 275-278 |
| 013 | 14 | | PA | 7-0 | 35-21-13 | SM00004 | | | | | | | SM00006 | | S | | 280-299 |
| 014 | 20 | | PA | 3-0 | 35-21-13 | SM00006 | | | | | | | D03024 | 1 | | | 050-099 |
| 014 | 20 | | PA | 4-0 | 35-21-13 | SM00006 | | | | | | | D03024 | 1 | | | 150-199, 275-299 |
| 015 | 20 | | PA | 3-0 | 35-21-13 | GD01714 | | D.. | E | | | | D03024 | 2 | | | 050-099 |
| 015 | 20 | | PA | 6-0 | 35-21-13 | GD05066 | | D.. | E | | | | D03024 | 2 | | | 150-199 |
| 015 | 20 | | PA | 5-0 | 35-21-13 | GD05066 | | D.. | E | | | | D03024 | 2 | | | 275-299 |
| 017 | 20 | | PA | 4-0 | 35-21-13 | SM00006 | | | | | | | D03026 | 1 | | | 050-099, 150-199, 280-299 |
| 017 | 20 | | PA | 3-0 | 35-21-13 | SM00006 | | | | | | | D03026 | 1 | | | 275-278 |
| 018 | 20 | | PA | 5-0 | 35-21-13 | GD01714 | | D.. | E | | | | D03026 | 2 | | | 050-099 |
| 018 | 20 | | PA | 3-0 | 35-21-13 | GD05066 | | D.. | E | | | | D03026 | 2 | | | 150-199, 275-299 |
| 019 | 16 | | PA | 8-0 | 35-21-13 | SM00008 | | | | | | | SM00006 | | S | | 050-099 |
| 019 | 14 | | PA | 8-0 | 35-21-13 | SM00008 | | | | | | | SM00021 | | S | | 150-199, 275-278 |
| 019 | 14 | | PA | 7-0 | 35-21-13 | SM00008 | | | | | | | SM00021 | | S | | 280-299 |
| 020 | 20 | | PA | 4-0 | 35-21-13 | SM00008 | | | | | | | D03028 | 1 | | | 050-099, 150-199 |
| 020 | 20 | | PA | 3-0 | 35-21-13 | SM00008 | | | | | | | D03028 | 1 | | | 275-299 |
| 021 | 20 | | PA | 6-0 | 35-21-13 | GD01720 | | D.. | E | | | | D03028 | 2 | | | 050-099 |
| 021 | 20 | | PA | 5-0 | 35-21-13 | GD05074 | | D.. | E | | | | D03028 | 2 | | | 150-199, 275-278 |
| 021 | 20 | | PA | 6-0 | 35-21-13 | GD05074 | | D.. | E | | | | D03028 | 2 | | | 280-299 |
| 023 | 20 | | PA | 3-0 | 35-21-13 | SM00008 | | | | | | | D03030 | 1 | | | 050-099, 150-199 |
| 023 | 20 | | PA | 4-0 | 35-21-13 | SM00008 | | | | | | | D03030 | 1 | | | 275-278 |
| 023 | 20 | | PA | 5-0 | 35-21-13 | SM00008 | | | | | | | D03030 | 1 | | | 280-299 |
| 024 | 20 | | PA | 3-0 | 35-21-13 | GD01720 | | D.. | E | | | | D03030 | 2 | | | 050-099 |
| 024 | 20 | | PA | 3-0 | 35-21-13 | GD05074 | | D.. | E | | | | D03030 | 2 | | | 150-199, 275-299 |
| 025 | 16 | | PA | 6-0 | 35-21-13 | SM00010 | | | | | | | SM00008 | | S | | 050-099 |
| 025 | 14 | | PA | 7-0 | 35-21-13 | SM00010 | | | | | | | SM00008 | | S | | 150-199, 275-278 |
| 025 | 14 | | PA | 8-0 | 35-21-13 | SM00010 | | | | | | | SM00008 | | S | | 280-299 |
| 027 | 20 | | PA | 3-0 | 35-21-13 | SM00010 | | | | | | | D03032 | 1 | | | 050-099, 150-199 |
| 027 | 20 | | PA | 4-0 | 35-21-13 | SM00010 | | | | | | | D03032 | 1 | | | 275-299 |
| 028 | 20 | | PA | 5-0 | 35-21-13 | GD01720 | | D.. | E | | | | D03032 | 2 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0728 | 286T0728 | | | R OXYGEN MASK DEPLOYMENT (continued) | | | | | | | | | | | |
| 028 | 20 | | PA | 5-0 | 35-21-13 | GD05074 | D.. | E | | D03032 | 2 | | | 150-199, 275-278 | |
| 028 | 20 | | PA | 6-0 | 35-21-13 | GD05074 | D.. | E | | D03032 | 2 | | | 280-299 | |
| 029 | 16 | | PA | 6-0 | 35-21-13 | SM00010 | | S | | SM00012 | | S | | 050-099 | |
| 029 | 14 | | PA | 7-0 | 35-21-13 | SM00010 | | S | | SM00012 | | S | | 150-199, 275-299 | |
| 030 | 20 | | PA | 4-0 | 35-21-13 | SM00010 | | S | | D03034 | 1 | | | ALL | |
| 031 | 20 | | PA | 5-0 | 35-21-13 | GD01726 | D.. | E | | D03034 | 2 | | | 050-099, 150-199, 275-278 | |
| 031 | 20 | | PA | 6-0 | 35-21-13 | GD01726 | D.. | E | | D03034 | 2 | | | 280-299 | |
| 033 | 20 | | PA | 4-0 | 35-21-13 | SM00012 | | S | | D03036 | 1 | | | 050-099, 150-199, 280-299 | |
| 033 | 20 | | PA | 3-0 | 35-21-13 | SM00012 | | S | | D03036 | 1 | | | 275-278 | |
| 034 | 20 | | PA | 3-0 | 35-21-13 | GD01726 | D.. | E | | D03036 | 2 | | | ALL | |
| 035 | 20 | | PA | 4-0 | 35-21-13 | SM00012 | | S | | D03038 | 1 | | | ALL | |
| 036 | 20 | | PA | 5-0 | 35-21-13 | GD01726 | D.. | E | | D03038 | 2 | | | 050-099, 150-199, 280-299 | |
| 036 | 20 | | PA | 4-0 | 35-21-13 | GD01726 | D.. | E | | D03038 | 2 | | | 275-278 | |
| 037 | 16 | | PA | 6-0 | 35-21-13 | SM00014 | | S | | SM00012 | | S | | 050-099 | |
| 037 | 14 | | PA | 6-0 | 35-21-13 | SM00014 | | S | | SM00012 | | S | | 150-199, 275-278 | |
| 037 | 14 | | PA | 5-0 | 35-21-13 | SM00014 | | S | | SM00012 | | S | | 280-299 | |
| 038 | 20 | | PA | 4-0 | 35-21-13 | SM00014 | | S | | D03040 | 1 | | | 050-099, 150-199 | |
| 038 | 20 | | PA | 3-0 | 35-21-13 | SM00014 | | S | | D03040 | 1 | | | 275-299 | |
| 039 | 20 | | PA | 5-0 | 35-21-13 | GD01730 | D.. | E | | D03040 | 2 | | | 050-099 | |
| 039 | 20 | | PA | 6-0 | 35-21-13 | GD01730 | D.. | E | | D03040 | 2 | | | 150-199, 275-278 | |
| 039 | 20 | | PA | 8-0 | 35-21-13 | GD01730 | D.. | E | | D03040 | 2 | | | 280-299 | |
| 041 | 20 | | PA | 4-0 | 35-21-13 | SM00014 | | S | | D03042 | 1 | | | 050-099, 150-199 | |
| 041 | 20 | | PA | 6-0 | 35-21-13 | SM00014 | | S | | D03042 | 1 | | | 275-278 | |
| 041 | 20 | | PA | 7-0 | 35-21-13 | SM00014 | | S | | D03042 | 1 | | | 280-299 | |
| 042 | 20 | | PA | 3-0 | 35-21-13 | GD01730 | D.. | E | | D03042 | 2 | | | 050-099, 150-199, 275-278 | |
| 042 | 20 | | PA | 4-0 | 35-21-13 | GD01730 | D.. | E | | D03042 | 2 | | | 280-299 | |
| 043 | 16 | | PA | 7-0 | 35-21-13 | SM00016 | | S | | SM00014 | | S | | 050-099 | |
| 043 | 14 | | PA | 6-0 | 35-21-13 | SM00016 | | S | | SM00014 | | S | | 150-199, 275-278 | |
| 043 | 14 | | PA | 7-0 | 35-21-13 | SM00016 | | S | | SM00014 | | S | | 280-299 | |
| 044 | 20 | | PA | 6-0 | 35-21-13 | SM00014 | | S | | D03044 | 1 | | | 050-099, 150-199 | |
| 044 | 20 | | PA | 7-0 | 35-21-13 | SM00014 | | S | | D03044 | 1 | | | 275-278 | |
| 044 | 20 | | PA | 8-0 | 35-21-13 | SM00014 | | S | | D03044 | 1 | | | 280-299 | |
| 045 | 20 | | PA | 4-0 | 35-21-13 | GD01730 | D.. | E | | D03044 | 2 | | | 050-099, 275-278 | |
| 045 | 20 | | PA | 3-0 | 35-21-13 | GD01730 | D.. | E | | D03044 | 2 | | | 150-199 | |
| 045 | 20 | | PA | 5-0 | 35-21-13 | GD01730 | D.. | E | | D03044 | 2 | | | 280-299 | |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0728 | 286T0728 | | | R OXYGEN MASK DEPLOYMENT (continued) | | | | | | | | | | | | | | |
| 047 | 20 | | PA | 13-0 | 35-21-13 | SM00016 | | | | | | | S | D03812 | 1 | | | 150-199 |
| 047 | 20 | | PA | 14-0 | 35-21-13 | SM00016 | | | | | | | S | D03812 | 1 | | | 275-278 |
| 047 | 20 | | PA | 15-0 | 35-21-13 | SM00016 | | | | | | | S | D03812 | 1 | | | 280-299 |
| 048 | 20 | | PA | 5-0 | 35-21-13 | GD00020 | | D.. | 2 | | | | | D03812 | 2 | | | 150-199, 275-299 |
| 050 | 20 | | PA | 20-0 | 35-21-13 | SM00016 | | | | | | | S | D03814 | 1 | | | 050-099 |
| 050 | 20 | | PA | 21-0 | 35-21-13 | SM00016 | | | | | | | S | D03814 | 1 | | | 150-199 |
| 050 | 20 | | PA | 22-0 | 35-21-13 | SM00016 | | | | | | | S | D03814 | 1 | | | 275-278 |
| 050 | 20 | | PA | 23-0 | 35-21-13 | SM00016 | | | | | | | S | D03814 | 1 | | | 280-299 |
| 051 | 20 | | PA | 14-0 | 35-21-13 | GD00020 | | D.. | 2 | | | | | D03814 | 2 | | | 050-099 |
| 051 | 20 | | PA | 15-0 | 35-21-13 | GD00020 | | D.. | 2 | | | | | D03814 | 2 | | | 150-199, 275-299 |
| 057 | 14 | | PA | 7-0 | 35-21-13 | SM00006 | | | | | | | S | SM00019 | | S | | 150-199, 275-278 |
| 057 | 14 | | PA | 6-0 | 35-21-13 | SM00006 | | | | | | | S | SM00019 | | S | | 280-299 |
| 059 | 14 | | PA | 6-0 | 35-21-13 | SM00019 | | | | | | | S | SM00021 | | S | | 150-199, 275-278 |
| 059 | 14 | | PA | 7-0 | 35-21-13 | SM00019 | | | | | | | S | SM00021 | | S | | 280-299 |
| 061 | 20 | | PA | 4-0 | 35-21-13 | SM00019 | | | | | | | S | D11274 | 1 | | | 150-199, 275-299 |
| 062 | 20 | | PA | 5-0 | 35-21-13 | GD05066 | | D.. | E | | | | | D11274 | 2 | | | 150-199, 275-299 |
| 063 | 20 | | PA | 4-0 | 35-21-13 | SM00019 | | | | | | | S | D11276 | 1 | | | 150-199 |
| 063 | 20 | | PA | 5-0 | 35-21-13 | SM00019 | | | | | | | S | D11276 | 1 | | | 275-299 |
| 064 | 20 | | PA | 5-0 | 35-21-13 | GD05070 | | D.. | E | | | | | D11276 | 2 | | | 150-199, 275-299 |
| 065 | 20 | | PA | 4-0 | 35-21-13 | SM00021 | | | | | | | S | D11278 | 1 | | | 150-199 |
| 065 | 20 | | PA | 3-0 | 35-21-13 | SM00021 | | | | | | | S | D11278 | 1 | | | 275-299 |
| 066 | 20 | | PA | 3-0 | 35-21-13 | GD05070 | | D.. | E | | | | | D11278 | 2 | | | 150-199, 275-299 |
| 067 | 20 | | PA | 4-0 | 35-21-13 | SM00021 | | | | | | | S | D11280 | 1 | | | 150-199, 275-278 |
| 067 | 20 | | PA | 5-0 | 35-21-13 | SM00021 | | | | | | | S | D11280 | 1 | | | 280-299 |
| 068 | 20 | | PA | 5-0 | 35-21-13 | GD05070 | | D.. | E | | | | | D11280 | 2 | | | 150-199, 275-299 |
| 072 | 14 | | PA | 5-0 | 35-21-13 | D06646P | | 2 | FN | | | | | SM00023 | | S | | 275-278 |
| 072 | 14 | | PA | 4-0 | 35-21-13 | D06646P | | 2 | FN | | | | | SM00023 | | S | | 280-299 |
| 073 | 20 | | PA | 4-0 | 35-21-13 | SM00023 | | | | | | | S | D01062 | 1 | | | 275-299 |
| 074 | 20 | | PA | 4-0 | 35-21-13 | D01062 | | 2 | | | | | | GD05046 | D.. | E | | 275-278 |
| 074 | 20 | | PA | 6-0 | 35-21-13 | D01062 | | 2 | | | | | | GD05046 | D.. | E | | 280-299 |
| 075 | 14 | | PA | 6-0 | 35-21-13 | SM00023 | | | | | | | S | SM00024 | | S | | 275-299 |
| 076 | 20 | | PA | 3-0 | 35-21-13 | SM00023 | | | | | | | S | D01004 | 1 | | | 275-278 |
| 076 | 20 | | PA | 4-0 | 35-21-13 | SM00023 | | | | | | | S | D01004 | 1 | | | 280-299 |
| 077 | 20 | | PA | 3-0 | 35-21-13 | D01004 | | 2 | | | | | | GD05046 | D.. | E | | 275-299 |
| 078 | 20 | | PA | 3-0 | 35-21-13 | SM00024 | | | | | | | S | D01094 | 1 | | | 275-278 |
| 078 | 20 | | PA | 4-0 | 35-21-13 | SM00024 | | | | | | | S | D01094 | 1 | | | 280-299 |
| 079 | 20 | | PA | 5-0 | 35-21-13 | D01094 | | 2 | | | | | | GD05046 | D.. | E | | 275-278 |
| 079 | 20 | | PA | 4-0 | 35-21-13 | D01094 | | 2 | | | | | | GD05046 | D.. | E | | 280-299 |
| 080 | 14 | | PA | 3-0 | 35-21-13 | D06646P | | 2 | FN | | | | | SM00025 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0728 | 286T0728 | | | R OXYGEN MASK DEPLOYMENT (continued) | | | | | | | | | | | |
| 080 | 14 | | PA | | 4-0 | 35-21-13 | SM00024 | | | | SM00025 | | S | | 275-299 |
| 081 | 20 | | PA | | 3-0 | 35-21-13 | SM00025 | | | | D11264 | 1 | | | 150-199 |
| 081 | 20 | | PA | | 4-0 | 35-21-13 | SM00024 | | | | D11264 | 1 | | | 275-278 |
| 081 | 20 | | PA | | 5-0 | 35-21-13 | SM00024 | | | | D11264 | 1 | | | 280-299 |
| 082 | 20 | | PA | | 5-0 | 35-21-13 | D11264 | 2 | | | GD05322 | D.. | E | | 150-199 |
| 082 | 20 | | PA | | 4-0 | 35-21-13 | D11264 | 2 | | | GD05050 | D.. | E | | 275-278 |
| 082 | 20 | | PA | | 5-0 | 35-21-13 | D11264 | 2 | | | GD05050 | D.. | E | | 280-299 |
| 083 | 20 | | PA | | 4-0 | 35-21-13 | SM00025 | | S | | D01096 | 1 | | | 150-199, 275-299 |
| 084 | 20 | | PA | | 3-0 | 35-21-13 | D01096 | 2 | | | GD05322 | D.. | E | | 150-199 |
| 084 | 20 | | PA | | 4-0 | 35-21-13 | D01096 | 2 | | | GD05050 | D.. | E | | 275-299 |
| 085 | 14 | | PA | | 6-0 | 35-21-13 | SM00025 | | S | | SM00026 | | S | | 150-199 |
| 085 | 14 | | PA | | 19-0 | 35-21-13 | SM00025 | | S | | SM00026 | | S | | 275-278 |
| 085 | 14 | | PA | | 20-0 | 35-21-13 | SM00025 | | S | | SM00026 | | S | | 280-299 |
| 088 | 20 | | PA | | 3-0 | 35-21-13 | SM00026 | | S | | D01098 | 1 | | | 150-199 |
| 088 | 20 | | PA | | 12-0 | 35-21-13 | SM00026 | | S | | D01100 | 1 | | | 275-278 |
| 088 | 20 | | PA | | 13-0 | 35-21-13 | SM00026 | | S | | D01100 | 1 | | | 280-299 |
| 089 | 20 | | PA | | 5-0 | 35-21-13 | D01098 | 2 | | | GD05322 | D.. | E | | 150-199 |
| 089 | 20 | | PA | | 6-0 | 35-21-13 | D01100 | 2 | | | GD04508 | D.. | E | | 275-278 |
| 089 | 20 | | PA | | 7-0 | 35-21-13 | D01100 | 2 | | | GD04508 | D.. | E | | 280-299 |
| 090 | 14 | | PA | | 6-0 | 35-21-13 | SM00026 | | S | | SM00027 | | S | | 150-199 |
| 090 | 14 | | PA | | 7-0 | 35-21-13 | SM00026 | | S | | SM00027 | | S | | 275-299 |
| 091 | 20 | | PA | | 4-0 | 35-21-13 | SM00026 | | S | | D01102 | 1 | | | 150-199 |
| 091 | 20 | | PA | | 9-0 | 35-21-13 | SM00026 | | S | | D01102 | 1 | | | 275-299 |
| 092 | 20 | | PA | | 6-0 | 35-21-13 | D01102 | 2 | | | GD05140 | D.. | E | | 150-199 |
| 092 | 20 | | PA | | 4-0 | 35-21-13 | D01102 | 2 | | | GD05448 | D.. | E | | 275-299 |
| 093 | 20 | | PA | | 3-0 | 35-21-13 | SM00027 | | S | | D01104 | 1 | | | 150-199 |
| 093 | 20 | | PA | | 4-0 | 35-21-13 | SM00027 | | S | | D01104 | 1 | | | 275-278 |
| 093 | 20 | | PA | | 5-0 | 35-21-13 | SM00027 | | S | | D01104 | 1 | | | 280-299 |
| 094 | 20 | | PA | | 3-0 | 35-21-13 | D01104 | 2 | | | GD05140 | D.. | E | | 150-199 |
| 094 | 20 | | PA | | 5-0 | 35-21-13 | D01104 | 2 | | | GD05054 | D.. | E | | 275-299 |
| 095 | 14 | | PA | | 24-0 | 35-21-13 | SM00027 | | S | | SM00028 | | S | | 150-199 |
| 095 | 14 | | PA | | 4-8 | 35-21-13 | SM00027 | | S | | SM00028 | | S | | 275-278 |
| 095 | 14 | | PA | | 6-0 | 35-21-13 | SM00027 | | S | | SM00028 | | S | | 280-299 |
| 096 | 20 | | PA | | 4-0 | 35-21-13 | SM00027 | | S | | D01106 | 1 | | | 150-199 |
| 096 | 20 | | PA | | 3-0 | 35-21-13 | SM00027 | | S | | D01106 | 1 | | | 275-299 |
| 097 | 20 | | PA | | 5-0 | 35-21-13 | D01106 | 2 | | | GD05140 | D.. | E | | 150-199 |
| 097 | 20 | | PA | | 3-0 | 35-21-13 | D01106 | 2 | | | GD05054 | D.. | E | | 275-299 |
| 098 | 20 | | PA | | 13-0 | 35-21-13 | SM00028 | | S | | D01108 | 1 | | | 150-199 |
| 098 | 20 | | PA | | 3-0 | 35-21-13 | SM00028 | | S | | D01108 | 1 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0720

Page 16

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0728 | 286T0728 | | | R OXYGEN MASK DEPLOYMENT (continued) | | | | | | | | | | | | | |
| 099 | 20 | | PA | 4-0 | 35-21-13 | D01108 | | 2 | | | | | GD04918 | D.. | E | | 150-199 |
| 099 | 20 | | PA | 5-0 | 35-21-13 | D01108 | | 2 | | | | | GD05054 | D.. | E | | 275-299 |
| 100 | 20 | | PA | 4-0 | 35-21-13 | SM00028 | | | | S | | | D01110 | | 1 | | 275-278 |
| 100 | 20 | | PA | 5-0 | 35-21-13 | SM00028 | | | | S | | | D01110 | | 1 | | 280-299 |
| 101 | 20 | | PA | 6-0 | 35-21-13 | D01110 | | 2 | | | | | GD05058 | D.. | E | | 275-299 |
| 103 | 20 | | PA | 7-0 | 35-21-13 | SM00028 | | | | S | | | D01112 | | 1 | | 150-199, 275-299 |
| 104 | 20 | | PA | 8-0 | 35-21-13 | D01112 | | 2 | | | | | GD05058 | D.. | E | | 150-199 |
| 104 | 20 | | PA | 3-0 | 35-21-13 | D01112 | | 2 | | | | | GD05058 | D.. | E | | 275-278 |
| 104 | 20 | | PA | 4-0 | 35-21-13 | D01112 | | 2 | | | | | GD05058 | D.. | E | | 280-299 |
| 105 | 20 | | PA | 4-0 | 35-21-13 | D13540 | | 1 | | | | | SM00001 | | S | | 150-199 |
| 106 | 20 | | PA | 4-0 | 35-21-13 | D13540 | | 2 | | | | | GD05646 | D.. | E | | 150-199 |
| 107 | 20 | | PA | 3-0 | 35-21-13 | D13542 | | 1 | | | | | SM00001 | | S | | 150-199 |
| 108 | 20 | | PA | 4-0 | 35-21-13 | D13542 | | 2 | | | | | GD05646 | D.. | E | | 150-199 |
| 109 | 20 | | PA | 17-0 | 35-21-13 | D12026 | | 2 | | | | | GD01730 | D.. | E | | 050-099 |
| 109 | 20 | | PA | 2-11 | 35-21-13 | D12026 | | 1 | | | | | SM00016 | | S | | 150-199 |
| 110 | 20 | | PA | 14-0 | 35-21-13 | D12026 | | 1 | | | | | SM00016 | | S | | 050-099 |
| 110 | 20 | | PA | 4-11 | 35-21-13 | D12026 | | 2 | | | | | GD01730 | D.. | E | | 150-199 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0731 | 286T0731 | | | CAPT EADI AND EHSI TO P10 & SHELF | | | | | | | | | | | |
| 001 | 24 | | PK | | 11-0 | 34-61-16 | D05809J | | | | TB0255X | C001 | BJ | | ALL |
| 002 | 24 | | PK | | 25-0 | 34-22-14 | D00107 | | | | D00469 | 24 | | | ALL |
| 003 | 24 | | PK | | 1-0 | 34-22-14 | D00107 | | | | SM00003 | | 9 | | ALL |
| 004 | 24 | | PK | | 1-0 | 34-22-14 | D00107 | | | | SM00002 | | 9 | | ALL |
| 005 | 24 | | PK | | 1-0 | 34-22-14 | D00107 | | | | SM00001 | | 9 | | ALL |
| 007 | 24 | | PK | | 25-0 | 34-22-14 | SM00003 | | 9 | | D05097J | 25 | | | ALL |
| 008 | 24 | | PK | | 25-0 | 34-22-14 | SM00002 | | 9 | | D05097J | 27 | | | ALL |
| 009 | 24 | | PK | | 25-0 | 34-22-14 | SM00001 | | 9 | | D05097J | 28 | | | ALL |
| 010 | 24 | | PK | | 26-0 | 34-22-35 | SM00003 | | 9 | | D05079J | 1 | | | ALL |
| 011 | 24 | | PK | | 26-0 | 34-22-35 | SM00002 | | 9 | | D05079J | 2 | | | ALL |
| 012 | 24 | | PK | | 26-0 | 34-22-35 | SM00001 | | 9 | | D05079J | 3 | | | ALL |
| 013 | 20 | | PA | | 0-6 | 34-22-16 | D00107 | | 17 | | GD00355 | S.. | 2 | | ALL |
| 014 | 20 | | PA | | 0-6 | 34-22-16 | D00107 | | 7 | | GD00355 | A.. | 2 | | ALL |
| 015 | 24 | | PK | | 6-0 | 34-22-16 | D00107 | | 6 | | D05809J | 6 | | | ALL |
| 021 | 24 | | PK | | 25-0 | 34-22-15 | D00109 | | 67 | | D00469 | 23 | | | ALL |
| 022 | 24 | | PK | | 2-0 | 34-22-15 | D00109 | | 22 | | SM00006 | | 9 | | ALL |
| 023 | 24 | | PK | | 2-0 | 34-22-15 | D00109 | | 23 | | SM00005 | | 9 | | ALL |
| 024 | 24 | | PK | | 2-0 | 34-22-15 | D00109 | | 24 | | SM00004 | | 9 | | ALL |
| 025 | 24 | | PK | | 5-0 | 34-22-15 | D00109 | | 1 | | D04867J | 3 | | | ALL |
| 026 | 24 | | PK | | 5-0 | 34-22-15 | D00109 | | 2 | | D04867J | 4 | | | ALL |
| 027 | 24 | | PK | | 5-0 | 34-22-15 | D00109 | | 8 | | D04867J | 5 | | | ALL |
| 028 | 24 | | PK | | 25-0 | 34-22-15 | SM00006 | | 9 | | D05101J | 25 | | | ALL |
| 029 | 24 | | PK | | 25-0 | 34-22-15 | SM00005 | | 9 | | D05101J | 27 | | | ALL |
| 030 | 24 | | PK | | 25-0 | 34-22-15 | SM00004 | | 9 | | D05101J | 28 | | | ALL |
| 031 | 24 | | PK | | 26-0 | 34-22-35 | SM00006 | | 9 | | D05079J | 8 | | | ALL |
| 032 | 24 | | PK | | 26-0 | 34-22-35 | SM00005 | | 9 | | D05079J | 7 | | | ALL |
| 033 | 24 | | PK | | 26-0 | 34-22-35 | SM00004 | | 9 | | D05079J | 6 | | | ALL |
| 034 | 20 | | PA | | 0-6 | 34-22-16 | D00109 | | 17 | | GD00359 | S.. | 2 | | ALL |
| 035 | 20 | | PA | | 0-6 | 34-22-16 | D00109 | | 7 | | GD00359 | A.. | 2 | | ALL |
| 036 | 24 | | PK | | 6-0 | 34-22-16 | D00109 | | 6 | | D05809J | 5 | | | ALL |
| 039 | 24 | | PK | | 22-0 | 34-22-16 | D00469 | | 3 | | D05809J | 4 | | | ALL |
| 040 | 20 | | PA | | 1-6 | 34-22-16 | D00469 | | 4 | | GD00603 | A.. | 2 | | ALL |
| 041 | 20 | | PA | | 1-6 | 34-22-16 | D00469 | | 34 | | GD00601 | D.. | 2 | | ALL |
| 042 | 20 | | PA | | 1-6 | 34-22-16 | D00469 | | 5 | | GD00607 | S.. | E | | ALL |
| 043 | 20 | | PA | | 1-6 | 34-22-16 | D00469 | | 38 | | GD00601 | D.. | 2 | | ALL |
| 044 | 24 | | PK | | 2-0 | 34-22-18 | D00469 | | 21 | | SM00009 | | 9 | | ALL |
| 045 | 24 | | PK | | 2-0 | 34-22-18 | D00469 | | 17 | | SM00009 | | 9 | | ALL |
| 046 | 24 | | PK | | 2-0 | 34-22-18 | D00469 | | 20 | | SM00008 | | 9 | | ALL |
| 047 | 24 | | PK | | 2-0 | 34-22-18 | D00469 | | 18 | | SM00008 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0730
 Page 1
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0731 | 286T0731 | | | CAPT EADI AND EHSI TO P10 & SHELF (continued) | | | | | | | | | | | | | |
| 048 | 20 | PA | | 1-6 | 34-22-18 | D00469 | | 16 | | | | | GD00601 | D.. | 2 | | ALL |
| 049 | 24 | PK | | 21-0 | 34-22-18 | D05809J | | 7 | | | | | SM00009 | | 9 | | ALL |
| 050 | 24 | PK | | 21-0 | 34-22-18 | D05809J | | 8 | | | | | SM00008 | | 9 | | ALL |
| 051 | 20 | PA | | 16-0 | 34-43-11 | D00469 | | 14 | | | | | SP00341 | | 9 | | 050-099, 151 |
| 051 | 20 | PA | | 16-0 | 34-43-11 | D00469 | | 14 | | | | | SP09003 | | 9 | | 150, 152-199, 275-299 |
| 053 | 24 | PK | | 24-0 | SPARE | D05809J | | 14 | | | | | D05079J | | 4 | | ALL |
| 054 | 24 | PK | | 24-0 | SPARE | D05809J | | 15 | | | | | D05079J | | 5 | | ALL |
| 055 | 24 | PK | | 28-0 | SPARE | D04867J | | 8 | | | | | D05079J | | 9 | | ALL |
| 056 | 24 | PK | | 28-0 | SPARE | D04867J | | 9 | | | | | D05079J | | 10 | | ALL |
| 072 | 16 | PA | | 15-0 | 33-13-18 | D00469 | | 1 | FM | | | | SP02288 | | 9 | | ALL |
| 073 | 16 | PA | | 1-6 | 33-13-18 | D00469 | | 2 | FM | | | | GD00603 | A.. | 2 | | ALL |
| 201B | 24 | PL | IA | 2-6 | 34-22-14 | D00107 | | 13 | | | | | D00109 | | 27 | | ALL |
| 201R | 24 | PL | IA | 0-0 | 34-22-14 | D00107 | | 12 | | | | | D00109 | | 26 | | ALL |
| 202B | 24 | PL | IB | 2-6 | 34-22-14 | D00107 | | 27 | | | | | D00109 | | 13 | | ALL |
| 202R | 24 | PL | IB | 0-0 | 34-22-14 | D00107 | | 26 | | | | | D00109 | | 12 | | ALL |
| 203B | 24 | PL | IC | 1-0 | 34-22-14 | D00107 | | 29 | | | | | SM00011 | | 9 | | ALL |
| 203R | 24 | PL | IC | 0-0 | 34-22-14 | D00107 | | 28 | | | | | SM00010 | | 9 | | ALL |
| 204W | 24 | BV | ID | 25-0 | 34-22-14 | D00107 | | 50 | | | | | D05097J | | 2 | | ALL |
| 204WN | 24 | BV | ID | 0-0 | 34-22-14 | D00107 | | 49 | | | | | D05097J | | 1 | | ALL |
| 204Z | | | ID | 0-0 | 34-22-14 | GD00353 | | S.. | 2 | | | | D05097J | | 19 | | ALL |
| 205W | 24 | BV | IE | 25-0 | 34-22-14 | D00107 | | 52 | | | | | D05097J | | 4 | | ALL |
| 205WN | 24 | BV | IE | 0-0 | 34-22-14 | D00107 | | 51 | | | | | D05097J | | 3 | | ALL |
| 205Z | | | IE | 0-0 | 34-22-14 | GD00353 | | S.. | 2 | | | | D05097J | | 20 | | ALL |
| 206W | 24 | BV | IF | 25-0 | 34-22-14 | D00107 | | 54 | | | | | D05097J | | 6 | | ALL |
| 206WN | 24 | BV | IF | 0-0 | 34-22-14 | D00107 | | 53 | | | | | D05097J | | 5 | | ALL |
| 206Z | | | IF | 0-0 | 34-22-14 | GD00353 | | S.. | 2 | | | | D05097J | | 21 | | ALL |
| 207W | 24 | BV | IG | 25-0 | 34-22-14 | D00107 | | 56 | | | | | D05097J | | 8 | | ALL |
| 207WN | 24 | BV | IG | 0-0 | 34-22-14 | D00107 | | 55 | | | | | D05097J | | 7 | | ALL |
| 207Z | | | IG | 0-0 | 34-22-14 | GD00353 | | S.. | 2 | | | | D05097J | | 22 | | ALL |
| 208W | 24 | BV | IH | 25-0 | 34-22-14 | D00107 | | 58 | | | | | D05097J | | 10 | | ALL |
| 208WN | 24 | BV | IH | 0-0 | 34-22-14 | D00107 | | 57 | | | | | D05097J | | 9 | | ALL |
| 208Z | | | IH | 0-0 | 34-22-14 | GD00355 | | S.. | 2 | | | | D05097J | | 23 | | ALL |
| 209W | 24 | BV | II | 25-0 | 34-22-14 | D00107 | | 60 | | | | | D05097J | | 12 | | ALL |
| 209WN | 24 | BV | II | 0-0 | 34-22-14 | D00107 | | 59 | | | | | D05097J | | 11 | | ALL |
| 209Z | | | II | 0-0 | 34-22-14 | GD00355 | | S.. | 2 | | | | D05097J | | 29 | | ALL |
| 210W | 24 | BV | IJ | 25-0 | 34-22-14 | D00107 | | 62 | | | | | D05097J | | 14 | | ALL |
| 210WN | 24 | BV | IJ | 0-0 | 34-22-14 | D00107 | | 61 | | | | | D05097J | | 13 | | ALL |
| 210Z | | | IJ | 0-0 | 34-22-14 | GD00355 | | S.. | 2 | | | | D05097J | | 30 | | ALL |
| 211W | 24 | BV | IK | 25-0 | 34-22-14 | D00107 | | 64 | | | | | D05097J | | 16 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0730

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0731 | 286T0731 | | | CAPT EADI AND EHSI TO P10 & SHELF (continued) | | | | | | | | | | | |
| 211WN | 24 | BV | IK | 0-0 | 34-22-14 | D00107 | 63 | | | D05097J | 15 | | | ALL | |
| 211Z | | | IK | 0-0 | 34-22-14 | GD00355 | S.. | 2 | | D05097J | 31 | | | ALL | |
| 212W | 24 | BV | IL | 25-0 | 34-22-14 | D00107 | 66 | | | D05097J | 18 | | | ALL | |
| 212WN | 24 | BV | IL | 0-0 | 34-22-14 | D00107 | 65 | | | D05097J | 17 | | | ALL | |
| 212Z | | | IL | 0-0 | 34-22-14 | GD00355 | S.. | 2 | | D05097J | 35 | | | ALL | |
| 213 | 20 | UA | | 1-6 | 34-22-14 | GD00615 | S.. | E | | D00469 | REF | | IM | ALL | |
| 213B | 24 | PW | IM | 27-0 | 34-22-14 | D05097J | 40 | | | D00469 | 35 | | | ALL | |
| 213R | 24 | PW | IM | 0-0 | 34-22-14 | D05097J | 39 | | | D00469 | 36 | | | ALL | |
| 213Z | | | IM | 0-0 | 34-22-14 | D05097J | 41 | | | D00469 | REF | | IM | ALL | |
| 214B | 24 | PL | IN | 2-0 | 34-22-15 | D00109 | 29 | | | SM00011 | | 9 | | ALL | |
| 214R | 24 | PL | IN | 0-0 | 34-22-15 | D00109 | 28 | | | SM00010 | | 9 | | ALL | |
| 215W | 24 | BV | IO | 26-0 | 34-22-15 | D00109 | 50 | | | D05101J | 2 | | | ALL | |
| 215WN | 24 | BV | IO | 0-0 | 34-22-15 | D00109 | 49 | | | D05101J | 1 | | | ALL | |
| 215Z | | | IO | 0-0 | 34-22-15 | GD00359 | S.. | 2 | | D05101J | 19 | | | ALL | |
| 216W | 24 | BV | IP | 26-0 | 34-22-15 | D00109 | 52 | | | D05101J | 4 | | | ALL | |
| 216WN | 24 | BV | IP | 0-0 | 34-22-15 | D00109 | 51 | | | D05101J | 3 | | | ALL | |
| 216Z | | | IP | 0-0 | 34-22-15 | GD00359 | S.. | 2 | | D05101J | 20 | | | ALL | |
| 217W | 24 | BV | IQ | 26-0 | 34-22-15 | D00109 | 54 | | | D05101J | 6 | | | ALL | |
| 217WN | 24 | BV | IQ | 0-0 | 34-22-15 | D00109 | 53 | | | D05101J | 5 | | | ALL | |
| 217Z | | | IQ | 0-0 | 34-22-15 | GD00359 | S.. | 2 | | D05101J | 21 | | | ALL | |
| 218W | 24 | BV | IR | 26-0 | 34-22-15 | D00109 | 56 | | | D05101J | 8 | | | ALL | |
| 218WN | 24 | BV | IR | 0-0 | 34-22-15 | D00109 | 55 | | | D05101J | 7 | | | ALL | |
| 218Z | | | IR | 0-0 | 34-22-15 | GD00359 | S.. | 2 | | D05101J | 22 | | | ALL | |
| 219W | 24 | BV | IS | 26-0 | 34-22-15 | D00109 | 58 | | | D05101J | 10 | | | ALL | |
| 219WN | 24 | BV | IS | 0-0 | 34-22-15 | D00109 | 57 | | | D05101J | 9 | | | ALL | |
| 219Z | | | IS | 0-0 | 34-22-15 | GD00361 | S.. | 2 | | D05101J | 23 | | | ALL | |
| 220W | 24 | BV | IT | 26-0 | 34-22-15 | D00109 | 60 | | | D05101J | 12 | | | ALL | |
| 220WN | 24 | BV | IT | 0-0 | 34-22-15 | D00109 | 59 | | | D05101J | 11 | | | ALL | |
| 220Z | | | IT | 0-0 | 34-22-15 | GD00361 | S.. | 2 | | D05101J | 29 | | | ALL | |
| 221W | 24 | BV | IU | 26-0 | 34-22-15 | D00109 | 62 | | | D05101J | 14 | | | ALL | |
| 221WN | 24 | BV | IU | 0-0 | 34-22-15 | D00109 | 61 | | | D05101J | 13 | | | ALL | |
| 221Z | | | IU | 0-0 | 34-22-15 | GD00361 | S.. | 2 | | D05101J | 30 | | | ALL | |
| 222W | 24 | BV | IV | 26-0 | 34-22-15 | D00109 | 64 | | | D05101J | 16 | | | ALL | |
| 222WN | 24 | BV | IV | 0-0 | 34-22-15 | D00109 | 63 | | | D05101J | 15 | | | ALL | |
| 222Z | | | IV | 0-0 | 34-22-15 | GD00361 | S.. | 2 | | D05101J | 31 | | | ALL | |
| 223W | 24 | BV | IW | 26-0 | 34-22-15 | D00109 | 66 | | | D05101J | 18 | | | ALL | |
| 223WN | 24 | BV | IW | 0-0 | 34-22-15 | D00109 | 65 | | | D05101J | 17 | | | ALL | |
| 223Z | | | IW | 0-0 | 34-22-15 | GD00361 | S.. | 2 | | D05101J | 35 | | | ALL | |
| 224B | 24 | PL | IX | 3-6 | 34-22-15 | D04867J | 2 | | | SM00011 | | 9 | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0730
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|----------|---------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0731 | 286T0731 | | | CAPT EADI AND EHSI TO P10 & SHELF (continued) | | | | | | | | | | | |
| 224R | 24 | PL | IX | 0-0 | 34-22-15 | D04867J | | 1 | | | SM00010 | | 9 | | ALL |
| 225B | 24 | PL | IY | 4-0 | 34-22-15 | D05809J | | 3 | | | SM00011 | | 9 | | ALL |
| 225R | 24 | PL | IY | 0-0 | 34-22-15 | D05809J | | 2 | | | SM00010 | | 9 | | ALL |
| 301B | 24 | PM | MA | 25-0 | 34-22-14 | D00107 | | 31 | | | D00469 | 32 | | | ALL |
| 301R | 24 | PM | MA | 0-0 | 34-22-14 | D00107 | | 30 | | | D00469 | 33 | | | ALL |
| 301Y | 24 | PM | MA | 0-0 | 34-22-14 | D00107 | | 32 | | | D00469 | 31 | | | ALL |
| 302B | 24 | PM | NB | 25-0 | 34-22-15 | D00109 | | 34 | | | D00469 | 29 | | | ALL |
| 302R | 24 | PM | NB | 0-0 | 34-22-15 | D00109 | | 33 | | | D00469 | 30 | | | ALL |
| 302Y | 24 | PM | NB | 0-0 | 34-22-15 | D00109 | | 35 | | | D00469 | 28 | | | ALL |
| 303B | 24 | PM | MC | 25-0 | 34-22-15 | D00109 | | 31 | | | D00469 | 26 | | | ALL |
| 303R | 24 | PM | MC | 0-0 | 34-22-15 | D00109 | | 30 | | | D00469 | 27 | | | ALL |
| 303Y | 24 | PM | MC | 0-0 | 34-22-15 | D00109 | | 32 | | | D00469 | 25 | | | ALL |
| W0733 | 286T0733 | | | F/O EADI AND EHSI TO P10 & SHELF | | | | | | | | | | | |
| 001 | 24 | PK | | 12-0 | 34-61-26 | D05813J | | 2 | | | TB0255X | D001 | BJ | | 150-199, 275-299 |
| 002 | 24 | PK | | 31-0 | 34-22-24 | D00807 | | 67 | | | D00471 | 24 | | | ALL |
| 003 | 24 | PK | | 1-0 | 34-22-24 | D00807 | | 22 | | | SM00003 | | 9 | | ALL |
| 004 | 24 | PK | | 1-0 | 34-22-24 | D00807 | | 23 | | | SM00002 | | 9 | | ALL |
| 005 | 24 | PK | | 1-0 | 34-22-24 | D00807 | | 24 | | | SM00001 | | 9 | | ALL |
| 007 | 24 | PK | | 33-0 | 34-22-24 | SM00003 | | 9 | | | D05081J | 25 | | | ALL |
| 008 | 24 | PK | | 33-0 | 34-22-24 | SM00002 | | 9 | | | D05081J | 27 | | | ALL |
| 009 | 24 | PK | | 33-0 | 34-22-24 | SM00001 | | 9 | | | D05081J | 28 | | | ALL |
| 010 | 24 | PK | | 33-0 | 34-22-34 | SM00003 | | 9 | | | D05389J | 1 | | | ALL |
| 011 | 24 | PK | | 33-0 | 34-22-34 | SM00002 | | 9 | | | D05389J | 2 | | | ALL |
| 012 | 24 | PK | | 33-0 | 34-22-34 | SM00001 | | 9 | | | D05389J | 3 | | | ALL |
| 013 | 24 | PK | | 11-0 | 34-22-26 | D00807 | | 6 | | | D05813J | 6 | | | ALL |
| 014 | 20 | PA | | 0-6 | 34-22-26 | D00807 | | 7 | | | GD00367 | A.. | 2 | | ALL |
| 015 | 20 | PA | | 0-6 | 34-22-26 | D00807 | | 17 | | | GD00367 | S.. | 2 | | ALL |
| 021 | 24 | PK | | 4-0 | 34-22-25 | D00809 | | 1 | | | D04869J | 3 | | | ALL |
| 022 | 24 | PK | | 4-0 | 34-22-25 | D00809 | | 2 | | | D04869J | 4 | | | ALL |
| 023 | 24 | PK | | 4-0 | 34-22-25 | D00809 | | 8 | | | D04869J | 5 | | | ALL |
| 024 | 24 | PK | | 30-0 | 34-22-25 | D00809 | | 67 | | | D00471 | 23 | | | ALL |
| 025 | 24 | PK | | 2-0 | 34-22-25 | D00809 | | 22 | | | SM00006 | | 9 | | ALL |
| 026 | 24 | PK | | 2-0 | 34-22-25 | D00809 | | 23 | | | SM00005 | | 9 | | ALL |
| 027 | 24 | PK | | 2-0 | 34-22-25 | D00809 | | 24 | | | SM00004 | | 9 | | ALL |
| 028 | 24 | PK | | 33-0 | 34-22-25 | SM00006 | | 9 | | | D05085J | 25 | | | ALL |
| 029 | 24 | PK | | 33-0 | 34-22-25 | SM00005 | | 9 | | | D05085J | 27 | | | ALL |
| 030 | 24 | PK | | 33-0 | 34-22-25 | SM00004 | | 9 | | | D05085J | 28 | | | ALL |
| 031 | 24 | PK | | 11-0 | 34-22-26 | D00809 | | 6 | | | D05813J | 5 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0730

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|---------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0733 | 286T0733 | | | F/O EADI AND EHSI TO P10 & SHELF (continued) | | | | | | | | | | | |
| 032 | 20 | | PA | | 0-6 | 34-22-26 | D00809 | | 7 | | GD00373 | A.. | 2 | | ALL |
| 033 | 20 | | PA | | 0-6 | 34-22-26 | D00809 | | 17 | | GD00373 | S.. | 2 | | ALL |
| 034 | 24 | | PK | | 33-0 | 34-22-34 | SM00004 | | | 9 | D05389J | | 6 | | ALL |
| 035 | 24 | | PK | | 33-0 | 34-22-34 | SM00005 | | | 9 | D05389J | | 7 | | ALL |
| 036 | 24 | | PK | | 33-0 | 34-22-34 | SM00006 | | | 9 | D05389J | | 8 | | ALL |
| 039 | 24 | | PK | | 23-0 | 34-22-26 | D00471 | | | 3 | D05813J | | 4 | | ALL |
| 040 | 20 | | PA | | 1-6 | 34-22-26 | D00471 | | | 4 | GD00609 | A.. | 2 | | ALL |
| 041 | 20 | | PA | | 1-6 | 34-22-26 | D00471 | | | 34 | GD00639 | D.. | 2 | | ALL |
| 042 | 20 | | PA | | 1-6 | 34-22-26 | D00471 | | | 5 | GD00619 | S.. | E | | ALL |
| 043 | 20 | | PA | | 1-6 | 34-22-26 | D00471 | | | 38 | GD00639 | D.. | 2 | | ALL |
| 044 | 24 | | PK | | 30-0 | 34-22-28 | D00471 | | | 21 | SM00009 | | 9 | | ALL |
| 045 | 24 | | PK | | 30-0 | 34-22-28 | D00471 | | | 17 | SM00009 | | 9 | | ALL |
| 046 | 24 | | PK | | 30-0 | 34-22-28 | D00471 | | | 20 | SM00008 | | 9 | | ALL |
| 047 | 24 | | PK | | 30-0 | 34-22-28 | D00471 | | | 18 | SM00008 | | 9 | | ALL |
| 048 | 20 | | PA | | 1-6 | 34-22-28 | D00471 | | | 16 | GD00639 | D.. | 2 | | ALL |
| 049 | 24 | | PK | | 11-0 | 34-22-28 | D05813J | | | 7 | SM00009 | | 9 | | ALL |
| 050 | 24 | | PK | | 11-0 | 34-22-28 | D05813J | | | 8 | SM00008 | | 9 | | ALL |
| 051 | 20 | | PA | | 17-0 | 34-43-11 | D00471 | | | 14 | SP00341 | | 9 | | 050-099, 151 |
| 051 | 20 | | PA | | 17-0 | 34-43-11 | D00471 | | | 14 | SP09004 | | 9 | | 150, 152-199, 275-299 |
| 053 | 24 | | PK | | 26-0 | SPARE | D05813J | | | 14 | D05389J | | 4 | | ALL |
| 054 | 24 | | PK | | 26-0 | SPARE | D05813J | | | 15 | D05389J | | 5 | | ALL |
| 055 | 24 | | PK | | 35-0 | SPARE | D04869J | | | 8 | D05389J | | 9 | | ALL |
| 056 | 24 | | PK | | 35-0 | SPARE | D04869J | | | 9 | D05389J | | 10 | | ALL |
| 072 | 16 | | PA | | 16-0 | 33-13-18 | D00471 | | | 1 | FM | SP02282 | | 9 | ALL |
| 073 | 16 | | PA | | 1-6 | 33-13-18 | D00471 | | | 2 | FM | GD00609 | A.. | 2 | 050-099, 150-154, 162-163, 275-276 |
| 073 | 16 | | PA | | 2-2 | 33-13-18 | D00471 | | | 2 | FM | GD00609 | A.. | 2 | 155-157, 164-199, 277-299 |
| 201B | 24 | | PL | IA | 2-0 | 34-22-24 | D00807 | | | 13 | D00809 | | 27 | | ALL |
| 201R | 24 | | PL | IA | 0-0 | 34-22-24 | D00807 | | | 12 | D00809 | | 26 | | ALL |
| 202B | 24 | | PL | IB | 2-0 | 34-22-24 | D00807 | | | 27 | D00809 | | 13 | | ALL |
| 202R | 24 | | PL | IB | 0-0 | 34-22-24 | D00807 | | | 26 | D00809 | | 12 | | ALL |
| 203B | 24 | | PL | IC | 1-0 | 34-22-24 | D00807 | | | 29 | SM00011 | | 9 | | ALL |
| 203R | 24 | | PL | IC | 0-0 | 34-22-24 | D00807 | | | 28 | SM00010 | | 9 | | ALL |
| 204W | 24 | | BV | ID | 34-0 | 34-22-24 | D00807 | | | 50 | D05081J | | 2 | | ALL |
| 204WN | 24 | | BV | ID | 0-0 | 34-22-24 | D00807 | | | 49 | D05081J | | 1 | | ALL |
| 204Z | | | | ID | 0-0 | 34-22-24 | GD00365 | | | S.. | 2 | D05081J | | 19 | ALL |
| 205W | 24 | | BV | IE | 34-0 | 34-22-24 | D00807 | | | 52 | D05081J | | 4 | | ALL |
| 205WN | 24 | | BV | IE | 0-0 | 34-22-24 | D00807 | | | 51 | D05081J | | 3 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0730
Page 5
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0733 | 286T0733 | | | F/O EADI AND EHSI TO P10 & SHELF (continued) | | | | | | | | | | | | |
| 205Z | | | IE | 0-0 | 34-22-24 | GD00365 | S.. | 2 | | D05081J | 20 | | | ALL | | |
| 206W | 24 | BV | IF | 34-0 | 34-22-24 | D00807 | | 54 | | D05081J | 6 | | | ALL | | |
| 206WN | 24 | BV | IF | 0-0 | 34-22-24 | D00807 | | 53 | | D05081J | 5 | | | ALL | | |
| 206Z | | | IF | 0-0 | 34-22-24 | GD00365 | S.. | 2 | | D05081J | 21 | | | ALL | | |
| 207W | 24 | BV | IG | 34-0 | 34-22-24 | D00807 | | 56 | | D05081J | 8 | | | ALL | | |
| 207WN | 24 | BV | IG | 0-0 | 34-22-24 | D00807 | | 55 | | D05081J | 7 | | | ALL | | |
| 207Z | | | IG | 0-0 | 34-22-24 | GD00365 | S.. | 2 | | D05081J | 22 | | | ALL | | |
| 208W | 24 | BV | IH | 34-0 | 34-22-24 | D00807 | | 58 | | D05081J | 10 | | | ALL | | |
| 208WN | 24 | BV | IH | 0-0 | 34-22-24 | D00807 | | 57 | | D05081J | 9 | | | ALL | | |
| 208Z | | | IH | 0-0 | 34-22-24 | GD00367 | S.. | 2 | | D05081J | 23 | | | ALL | | |
| 209W | 24 | BV | II | 34-0 | 34-22-24 | D00807 | | 60 | | D05081J | 12 | | | ALL | | |
| 209WN | 24 | BV | II | 0-0 | 34-22-24 | D00807 | | 59 | | D05081J | 11 | | | ALL | | |
| 209Z | | | II | 0-0 | 34-22-24 | GD00367 | S.. | 2 | | D05081J | 29 | | | ALL | | |
| 210W | 24 | BV | IJ | 34-0 | 34-22-24 | D00807 | | 62 | | D05081J | 14 | | | ALL | | |
| 210WN | 24 | BV | IJ | 0-0 | 34-22-24 | D00807 | | 61 | | D05081J | 13 | | | ALL | | |
| 210Z | | | IJ | 0-0 | 34-22-24 | GD00367 | S.. | 2 | | D05081J | 30 | | | ALL | | |
| 211W | 24 | BV | IK | 34-0 | 34-22-24 | D00807 | | 64 | | D05081J | 16 | | | ALL | | |
| 211WN | 24 | BV | IK | 0-0 | 34-22-24 | D00807 | | 63 | | D05081J | 15 | | | ALL | | |
| 211Z | | | IK | 0-0 | 34-22-24 | GD00367 | S.. | 2 | | D05081J | 31 | | | ALL | | |
| 212W | 24 | BV | IL | 34-0 | 34-22-24 | D00807 | | 66 | | D05081J | 18 | | | ALL | | |
| 212WN | 24 | BV | IL | 0-0 | 34-22-24 | D00807 | | 65 | | D05081J | 17 | | | ALL | | |
| 212Z | | | IL | 0-0 | 34-22-24 | GD00367 | S.. | 2 | | D05081J | 35 | | | ALL | | |
| 213 | 20 | UA | | 1-6 | 34-22-24 | GD00621 | S.. | E | | D00471 | REF | | IM | ALL | | |
| 213B | 24 | PW | IM | 33-0 | 34-22-24 | D05081J | | 40 | | D00471 | 35 | | | ALL | | |
| 213R | 24 | PW | IM | 0-0 | 34-22-24 | D05081J | | 39 | | D00471 | 36 | | | ALL | | |
| 213Z | | | IM | 0-0 | 34-22-24 | D05081J | | 41 | | D00471 | REF | | IM | ALL | | |
| 214B | 24 | PL | IN | 2-0 | 34-22-25 | D00809 | | 29 | | SM00011 | | 9 | | ALL | | |
| 214R | 24 | PL | IN | 0-0 | 34-22-25 | D00809 | | 28 | | SM00010 | | 9 | | ALL | | |
| 215W | 24 | BV | IO | 34-0 | 34-22-25 | D00809 | | 50 | | D05085J | 2 | | | ALL | | |
| 215WN | 24 | BV | IO | 0-0 | 34-22-25 | D00809 | | 49 | | D05085J | 1 | | | ALL | | |
| 215Z | | | IO | 0-0 | 34-22-25 | GD00371 | S.. | 2 | | D05085J | 19 | | | ALL | | |
| 216W | 24 | BV | IP | 34-0 | 34-22-25 | D00809 | | 52 | | D05085J | 4 | | | ALL | | |
| 216WN | 24 | BV | IP | 0-0 | 34-22-25 | D00809 | | 51 | | D05085J | 3 | | | ALL | | |
| 216Z | | | IP | 0-0 | 34-22-25 | GD00371 | S.. | 2 | | D05085J | 20 | | | ALL | | |
| 217W | 24 | BV | IQ | 34-0 | 34-22-25 | D00809 | | 54 | | D05085J | 6 | | | ALL | | |
| 217WN | 24 | BV | IQ | 0-0 | 34-22-25 | D00809 | | 53 | | D05085J | 5 | | | ALL | | |
| 217Z | | | IQ | 0-0 | 34-22-25 | GD00371 | S.. | 2 | | D05085J | 21 | | | ALL | | |
| 218W | 24 | BV | IR | 34-0 | 34-22-25 | D00809 | | 56 | | D05085J | 8 | | | ALL | | |
| 218WN | 24 | BV | IR | 0-0 | 34-22-25 | D00809 | | 55 | | D05085J | 7 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0730

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0733 | 286T0733 | | | F/O EADI AND EHSI TO P10 & SHELF (continued) | | | | | | | | | | | |
| 218Z | | | | IR | 0-0 | 34-22-25 | GD00371 | S.. | 2 | | D05085J | 22 | | | ALL |
| 219W | 24 | | BV | IS | 34-0 | 34-22-25 | D00809 | | 58 | | D05085J | 10 | | | ALL |
| 219WN | 24 | | BV | IS | 0-0 | 34-22-25 | D00809 | | 57 | | D05085J | 9 | | | ALL |
| 219Z | | | | IS | 0-0 | 34-22-25 | GD00373 | S.. | 2 | | D05085J | 23 | | | ALL |
| 220W | 24 | | BV | IT | 34-0 | 34-22-25 | D00809 | | 60 | | D05085J | 12 | | | ALL |
| 220WN | 24 | | BV | IT | 0-0 | 34-22-25 | D00809 | | 59 | | D05085J | 11 | | | ALL |
| 220Z | | | | IT | 0-0 | 34-22-25 | GD00373 | S.. | 2 | | D05085J | 29 | | | ALL |
| 221W | 24 | | BV | IU | 34-0 | 34-22-25 | D00809 | | 62 | | D05085J | 14 | | | ALL |
| 221WN | 24 | | BV | IU | 0-0 | 34-22-25 | D00809 | | 61 | | D05085J | 13 | | | ALL |
| 221Z | | | | IU | 0-0 | 34-22-25 | GD00373 | S.. | 2 | | D05085J | 30 | | | ALL |
| 222W | 24 | | BV | IV | 34-0 | 34-22-25 | D00809 | | 64 | | D05085J | 16 | | | ALL |
| 222WN | 24 | | BV | IV | 0-0 | 34-22-25 | D00809 | | 63 | | D05085J | 15 | | | ALL |
| 222Z | | | | IV | 0-0 | 34-22-25 | GD00373 | S.. | 2 | | D05085J | 31 | | | ALL |
| 223W | 24 | | BV | IW | 34-0 | 34-22-25 | D00809 | | 66 | | D05085J | 18 | | | ALL |
| 223WN | 24 | | BV | IW | 0-0 | 34-22-25 | D00809 | | 65 | | D05085J | 17 | | | ALL |
| 223Z | | | | IW | 0-0 | 34-22-25 | GD00373 | S.. | 2 | | D05085J | 35 | | | ALL |
| 224B | 24 | | PL | IX | 3-0 | 34-22-25 | D04869J | | 2 | | SM00011 | | 9 | | ALL |
| 224R | 24 | | PL | IX | 0-0 | 34-22-25 | D04869J | | 1 | | SM00010 | | 9 | | ALL |
| 301B | 24 | | PM | MA | 31-0 | 34-22-24 | D00807 | | 31 | | D00471 | 32 | | | ALL |
| 301R | 24 | | PM | MA | 0-0 | 34-22-24 | D00807 | | 30 | | D00471 | 33 | | | ALL |
| 301Y | 24 | | PM | MA | 0-0 | 34-22-24 | D00807 | | 32 | | D00471 | 31 | | | ALL |
| 302B | 24 | | PM | MB | 30-0 | 34-22-25 | D00809 | | 34 | | D00471 | 29 | | | ALL |
| 302R | 24 | | PM | MB | 0-0 | 34-22-25 | D00809 | | 33 | | D00471 | 30 | | | ALL |
| 302Y | 24 | | PM | MB | 0-0 | 34-22-25 | D00809 | | 35 | | D00471 | 28 | | | ALL |
| 303B | 24 | | PM | MC | 30-0 | 34-22-25 | D00809 | | 31 | | D00471 | 26 | | | ALL |
| 303R | 24 | | PM | MC | 0-0 | 34-22-25 | D00809 | | 30 | | D00471 | 27 | | | ALL |
| 303Y | 24 | | PM | MC | 0-0 | 34-22-25 | D00809 | | 32 | | D00471 | 25 | | | ALL |
| W0738 | 286T0738 | | | RIGHT AIR COND PACK,ISOL VLV | | | | | | | | | | | |
| 005 | 22 | | PA | | 65-8 | 32-42-11 | D05230J | | 5 | | D04538J | 5 | | | 050-099 |
| 005 | 22 | | PA | | 75-9 | 32-42-11 | D05230J | | 5 | | D04538J | 5 | | | 150-199, 275-299 |
| 006 | 22 | | PA | | 65-8 | 32-42-11 | D05230J | | 6 | | D04538J | 6 | | | 050-099 |
| 006 | 22 | | PA | | 75-9 | 32-42-11 | D05230J | | 6 | | D04538J | 6 | | | 150-199, 275-299 |
| 007 | 22 | | PA | | 65-8 | 32-42-11 | D05230J | | 7 | | D04538J | 7 | | | 050-099 |
| 007 | 22 | | PA | | 75-9 | 32-42-11 | D05230J | | 7 | | D04538J | 7 | | | 150-199, 275-299 |
| 008 | 20 | | PA | | 4-6 | 32-42-11 | GD00854 | D.. | 2 | | D04538J | 8 | | | ALL |
| 009 | 20 | | PA | | 4-6 | 32-42-11 | GD00854 | D.. | 2 | | D04538J | 9 | | | ALL |
| 010 | 20 | | PA | | 4-6 | 32-42-11 | GD00854 | D.. | 2 | | D04538J | 10 | | | ALL |
| 015 | 24 | | PK | | 48-7 | 21-51-21 | D04004P | | 9 | | D05136J | 15 | | | 050-099 |

WIRE LIST

D280T132

91-21-11
Section W0730
Page 7
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0738 | 286T0738 | | | RIGHT AIR COND PACK,ISOL VLV (continued) | | | | | | | | | | | |
| 015 | 24 | | PK | 59-3 | 21-51-21 | D04004P | | 9 | | | D05136J | | 15 | | 150-199, 275-299 |
| 016 | 20 | | PQ | A | 63-5 | 28-41-22 | D04638J | | 1 | | D04538J | | 1 | | 050-099 |
| 016 | 20 | | PQ | A | 73-7 | 28-41-22 | D04638J | | 1 | | D04538J | | 1 | | 150-199, 275-299 |
| 016Z | | | | A | 0-0 | 28-41-22 | D04638J | | = C1 | | D04538J | | = C1 | | ALL |
| 017 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 5 | | | D04268J | | 1 | | 050-099 |
| 017 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 5 | | | D04268J | | 1 | | 150-199, 275-299 |
| 018 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 6 | | | D04268J | | 2 | | 050-099 |
| 018 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 6 | | | D04268J | | 2 | | 150-199, 275-299 |
| 019 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 7 | | | D04268J | | 3 | | 050-099 |
| 019 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 7 | | | D04268J | | 3 | | 150-199, 275-299 |
| 020 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 28 | | | D04268J | | 4 | | 050-099 |
| 020 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 28 | | | D04268J | | 4 | | 150-199, 275-299 |
| 021 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 29 | | | D04268J | | 5 | | 050-099 |
| 021 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 29 | | | D04268J | | 5 | | 150-199, 275-299 |
| 022 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 10 | | | D04268J | | 6 | | 050-099 |
| 022 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 10 | | | D04268J | | 6 | | 150-199, 275-299 |
| 023 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 11 | | | D04268J | | 7 | | 050-099 |
| 023 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 11 | | | D04268J | | 7 | | 150-199, 275-299 |
| 024 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 12 | | | D04268J | | 8 | | 050-099 |
| 024 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 12 | | | D04268J | | 8 | | 150-199, 275-299 |
| 025 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 13 | | | D04268J | | 9 | | 050-099 |
| 025 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 13 | | | D04268J | | 9 | | 150-199, 275-299 |
| 026 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 14 | | | D04268J | | 10 | | 050-099 |
| 026 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 14 | | | D04268J | | 10 | | 150-199, 275-299 |
| 027 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 15 | | | D04268J | | 11 | | 050-099 |
| 027 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 15 | | | D04268J | | 11 | | 150-199, 275-299 |
| 028 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 16 | | | D04268J | | 12 | | 050-099 |
| 028 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 16 | | | D04268J | | 12 | | 150-199, 275-299 |
| 029 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 17 | | | D04268J | | 13 | | 050-099 |
| 029 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 17 | | | D04268J | | 13 | | 150-199, 275-299 |
| 030 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 18 | | | D04268J | | 14 | | 050-099 |
| 030 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 18 | | | D04268J | | 14 | | 150-199, 275-299 |
| 031 | 24 | | PK | 63-3 | 28-41-22 | D04804J | | 19 | | | D04268J | | 15 | | 050-099 |
| 031 | 24 | | PK | 73-5 | 28-41-22 | D04804J | | 19 | | | D04268J | | 15 | | 150-199, 275-299 |
| 032 | 22 | | PA | 77-0 | 28-41-22 | D04716P | | 1 | | | D04418J | | 10 | | 050-099 |
| 032 | 22 | | PA | 87-1 | 28-41-22 | D04716P | | 1 | | | D04418J | | 10 | | 150-199, 275-299 |
| 033 | 22 | | PA | 77-0 | 28-41-23 | D04716P | | 2 | | | D04418J | | 5 | | 050-099 |
| 033 | 22 | | PA | 87-1 | 28-41-23 | D04716P | | 2 | | | D04418J | | 5 | | 150-199, 275-299 |
| 038 | 24 | | PK | 26-5 | 21-58-11 | D03066 | | 1 | | | SM00001 | | | S | ALL |

WIRE LIST

D280T132

91-21-11

Section W0730

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0738 | 286T0738 | | | RIGHT AIR COND PACK,ISOL VLV (continued) | | | | | | | | | | | |
| 039 | 24 | | PK | | 44-1 | 21-58-11 | D03066 | | | | D04004P | 22 | | | ALL |
| 040 | 20 | | PA | | 4-10 | 21-58-11 | D03066 | | | | GD04204 | D.. | E | | ALL |
| 041 | 20 | | PA | | 5-0 | 21-58-11 | D03066 | | | | GD01384 | S.. | E | | ALL |
| 042 | 24 | | PK | | 28-0 | 21-58-11 | D03068 | | | | SM00001 | | S | | ALL |
| 043 | 24 | | PK | | 17-6 | 21-58-11 | D03068 | | | | D04004P | 20 | | | ALL |
| 044 | 20 | | PA | | 5-0 | 21-58-11 | D03068 | | | | GD00595 | D.. | 2 | | ALL |
| 045 | 20 | | PA | | 4-11 | 21-58-11 | D03068 | | | | GD00595 | S.. | 2 | | ALL |
| 046 | 24 | | PK | | 18-8 | 21-58-11 | D04004P | 21 | | | SM00001 | | S | | ALL |
| 047 | 20 | | PA | | 31-4 | 33-42-11 | D05266P | 10 | | | D04716P | 7 | | | ALL |
| 048 | 20 | | PA | | 31-4 | 33-42-11 | D05266P | 11 | | | D04716P | 8 | | | ALL |
| 049 | 24 | | PK | | 48-6 | 36-11-21 | D04004P | 11 | | | D05056J | 19 | | | 050-099 |
| 049 | 24 | | PK | | 59-1 | 36-11-21 | D04004P | 11 | | | D05056J | 19 | | | 150-199, 275-299 |
| 050 | 24 | | PK | | 48-6 | 36-11-21 | D04004P | 12 | | | D05056J | 20 | | | 050-099 |
| 050 | 24 | | PK | | 59-1 | 36-11-21 | D04004P | 12 | | | D05056J | 20 | | | 150-199, 275-299 |
| 051 | 24 | | PK | | 48-6 | 36-11-21 | D04004P | 13 | | | D05056J | 21 | | | 050-099 |
| 051 | 24 | | PK | | 59-1 | 36-11-21 | D04004P | 13 | | | D05056J | 21 | | | 150-199, 275-299 |
| 052 | 24 | | PK | | 48-6 | 36-11-21 | D04004P | 14 | | | D05056J | 22 | | | 050-099 |
| 052 | 24 | | PK | | 59-1 | 36-11-21 | D04004P | 14 | | | D05056J | 22 | | | 150-199, 275-299 |
| 053 | 24 | | PK | | 33-6 | 36-23-21 | D04716P | 11 | | | D08050J | 34 | | | ALL |
| 054 | 24 | | PK | | 33-6 | 36-23-21 | D04716P | 12 | | | D08050J | 35 | | | ALL |
| 057 | 20 | | PQ | AS | 63-5 | 28-41-23 | D05878J | 1 | | | D06080J | 1 | | | 050-099 |
| 057 | 20 | | PQ | AS | 73-6 | 28-41-23 | D05878J | 1 | | | D06080J | 1 | | | 150-199, 275-299 |
| 057Z | | | | AS | 0-0 | 28-41-23 | D05878J | =C1 | | | D06080J | =C1 | | | ALL |
| 058 | 24 | | PK | | 63-3 | 28-41-23 | D04804J | 30 | | | D05880J | 5 | | | 050-099 |
| 058 | 24 | | PK | | 73-5 | 28-41-23 | D04804J | 30 | | | D05880J | 5 | | | 150-199, 275-299 |
| 060 | 24 | | PK | | 63-3 | 28-41-23 | D04804J | 32 | | | D05880J | 7 | | | 050-099 |
| 060 | 24 | | PK | | 73-5 | 28-41-23 | D04804J | 32 | | | D05880J | 7 | | | 150-199, 275-299 |
| 061 | 24 | | PK | | 63-3 | 28-41-23 | D04804J | 33 | | | D05880J | 2 | | | 050-099 |
| 061 | 24 | | PK | | 73-5 | 28-41-23 | D04804J | 33 | | | D05880J | 2 | | | 150-199, 275-299 |
| 062 | 24 | | PK | | 63-3 | 28-41-23 | D04804J | 34 | | | D05880J | 3 | | | 050-099 |
| 062 | 24 | | PK | | 73-5 | 28-41-23 | D04804J | 34 | | | D05880J | 3 | | | 150-199, 275-299 |
| 063 | 24 | | PK | | 63-3 | 28-41-23 | D04804J | 35 | | | D05880J | 4 | | | 050-099 |
| 063 | 24 | | PK | | 73-5 | 28-41-23 | D04804J | 35 | | | D05880J | 4 | | | 150-199, 275-299 |
| 065 | 22 | | PA | | 25-0 | 28-41-12 | D04716P | 13 | | | D04804J | 9 | | | ALL |
| 068 | 20 | | PA | | 25-0 | SPARE | D04804J | 26 | | | D04716P | 16 | | | ALL |
| 070 | 24 | | PK | | 31-4 | SPARE | D05266P | 1 | | | D04716P | 18 | | | ALL |
| 071 | 24 | | PK | | 31-4 | SPARE | D05266P | 2 | | | D04716P | 19 | | | ALL |
| 074 | 22 | | PA | | 31-4 | 27-09-12 | D04716P | 25 | | | D04004P | 4 | | | ALL |
| 080 | 24 | | PK | | 31-4 | 30-21-11 | D04716P | 4 | | | D04004P | 8 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0730

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|---------|-------------|---|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0738 | 286T0738 | | | RIGHT AIR COND PACK,ISOL VLV (continued) | | | | | | | | | | | | | |
| 082 | 22 | PA | | 50-8 | SPARE | D08050J | 29 | | | | | | D05056J | 23 | | | 050-099 |
| 082 | 22 | PA | | 61-3 | SPARE | D08050J | 29 | | | | | | D05056J | 23 | | | 150-199, 275-299 |
| 083 | 22 | PA | | 63-3 | SPARE | D04804J | 40 | | | | | | D04538J | 2 | | | 050-099 |
| 083 | 22 | PA | | 73-4 | SPARE | D04804J | 40 | | | | | | D04538J | 2 | | | 150-199, 275-299 |
| 084 | 22 | PA | | 65-8 | SPARE | D05230J | 8 | | | | | | D05880J | 8 | | | 050-099 |
| 084 | 22 | PA | | 75-10 | SPARE | D05230J | 8 | | | | | | D05880J | 8 | | | 150-199, 277-278 |
| 085 | 22 | PA | | 65-8 | SPARE | D05230J | 10 | | | | | | D04268J | 16 | | | 050-099 |
| 085 | 22 | PA | | 75-10 | SPARE | D05230J | 10 | | | | | | D04268J | 16 | | | 150-199, 275-299 |
| 086 | 24 | PK | | 48-7 | 21-51-21 | D04004P | 6 | | | | | | D05136J | 32 | | | 050-099 |
| 086 | 24 | PK | | 59-3 | 21-51-21 | D04004P | 6 | | | | | | D05136J | 32 | | | 150-199, 275-299 |
| 091 | 24 | PK | | 44-1 | 21-58-11 | D05266P | 20 | | | | | | D03066 | 5 | | | ALL |
| 092 | 24 | PK | | 17-6 | 21-58-11 | D05266P | 21 | | | | | | D03068 | 5 | | | ALL |
| 094 | 24 | PK | | 25-0 | 24-22-22 | D04716P | 26 | | | | | | D04804J | 31 | | | ALL |
| 097 | 24 | PK | | 0-7 | SPARE | D06236P | | CAP | Y | | | | D06236P | A13 | \$D | | ALL |
| 098 | 24 | PK | | 0-7 | SPARE | D06236P | | CAP | Y | | | | D06236P | A12 | \$D | | ALL |
| 099 | 20 | PA | | 31-4 | 25-31-11 | D04716P | 29 | | | | | | D05266P | 23 | | | 050-099, 150-199 |
| 099 | 20 | PA | | 25-0 | 25-31-11 | D04716P | 29 | | | | | | D04804J | 22 | | | 275-276 |
| 101 | 24 | PK | | 48-7 | 36-21-11 | D04004P | 7 | | | | | | D05136J | 11 | | | 050-099 |
| 101 | 24 | PK | | 59-3 | 36-21-11 | D04004P | 7 | | | | | | D05136J | 11 | | | 150-199, 275-299 |
| 102 | 24 | PK | | 37-7 | 21-61-51 | D08050J | 47 | | | | | | D06236P | A14 | \$D | | ALL |
| 105 | 24 | PK | | 35-5 | 73-21-14 | D04004P | 3 | | | | | | D06236P | A15 | \$D | | ALL |
| 106 | 24 | PK | | 37-7 | 21-51-21 | D08050J | 48 | | | | | | D06236P | B14 | \$D | | ALL |
| 107 | 20 | PQ | BM | 31-4 | 27-32-31 | D04716P | 6 | | | | | | D05266P | 22 | | | ALL |
| 107Z | | | BM | 0-0 | 27-32-31 | D04716P | | DED | | | | | D05266P | DED | | | ALL |
| 108 | 22 | PQ | H | 31-4 | 29-11-12 | D04004P | 29 | | | | | | D04716P | 31 | | | ALL |
| 108Z | | | H | 0-0 | 29-11-12 | D04004P | | DED | | | | | D04716P | DED | | | ALL |
| 109 | 24 | PK | | 31-4 | SPARE | D04004P | 26 | | | | | | D04716P | 28 | | | 050-099, 150-155, 162-165, 275-276 |
| 109 | 24 | PK | | 31-4 | SPARE | D04004P | | CAP | Y | | | | D04716P | 28 | | | 156-157, 166-199, 277-299 |
| 115 | 24 | PK | | 5-1 | 36-23-21 | D08050J | 42 | | | | | | D04004P | 10 | | | ALL |
| 117 | 24 | PK | | 5-1 | 36-23-21 | D04004P | 25 | | | | | | D08050J | 52 | | | ALL |
| 118 | 24 | PK | | 5-1 | 36-23-21 | D04004P | 27 | | | | | | D08050J | 53 | | | ALL |
| 119 | 24 | PK | | 5-1 | 36-23-21 | D04004P | 28 | | | | | | D08050J | 54 | | | ALL |
| 124 | 20 | UA | | 6-0 | 78-34-21 | D04716P | | | | | | | FB | GD00670 | S.. | 2 | 050-099, 150-156, 162-166, 275-276 |
| 124 | 20 | UA | | 5-0 | 78-34-21 | D04716P | | | | | | | FB | GD00670 | S.. | 2 | 157, 167-199, 277-299 |
| 125 | 20 | UA | | 5-0 | 78-34-21 | D05266P | | | | | | | FA | GD00754 | S.. | 2 | ALL |
| 126 | 20 | PQ | FA | 31-4 | 78-34-21 | D05266P | 12 | | | | | | D04716P | 5 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0730

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0738 | 286T0738 | | | RIGHT AIR COND PACK,ISOL VLV (continued) | | | | | | | | | | | | |
| 126Z | | | | FA | 0-0 | 78-34-21 | D05266P | | | | FA | D04716P | | | FB | ALL |
| 127 | 20 | PQ | | FB | 31-4 | 78-34-21 | D05266P | 13 | | | | D04716P | 27 | | | ALL |
| 127Z | | | | FB | 0-0 | 78-34-21 | D05266P | | | | FA | D04716P | | | FB | ALL |
| 201B | 24 | PL | AD | | 63-3 | 28-41-22 | D04804J | 1 | | | | D04418J | 6 | | | 050-099 |
| 201B | 24 | PL | AD | | 73-5 | 28-41-22 | D04804J | 1 | | | | D04418J | 6 | | | 150-199, 275-299 |
| 201R | 24 | PL | AD | | 0-0 | 28-41-22 | D04804J | 2 | | | | D04418J | 7 | | | ALL |
| 203B | 24 | PL | AH | | 63-3 | 28-41-23 | D04804J | 20 | | | | D04418J | 1 | | | 050-099 |
| 203B | 24 | PL | AH | | 73-5 | 28-41-23 | D04804J | 20 | | | | D04418J | 1 | | | 150-199, 275-299 |
| 203R | 24 | PL | AH | | 0-0 | 28-41-23 | D04804J | 21 | | | | D04418J | 2 | | | ALL |
| 206B | 22 | PB | AN | | 50-9 | 21-51-22 | D08050J | 19 | | | | D05136J | 19 | | | 050-099 |
| 206B | 22 | PB | AN | | 61-5 | 21-51-22 | D08050J | 19 | | | | D05136J | 19 | | | 150-199, 275-299 |
| 206R | 22 | PB | AN | | 0-0 | 21-51-22 | D08050J | 20 | | | | D05136J | 20 | | | ALL |
| 207B | 22 | PB | AO | | 50-9 | 21-51-22 | D08050J | 21 | | | | D05136J | 21 | | | 050-099 |
| 207B | 22 | PB | AO | | 61-5 | 21-51-22 | D08050J | 21 | | | | D05136J | 21 | | | 150-199, 275-299 |
| 207R | 22 | PB | AO | | 0-0 | 21-51-22 | D08050J | 22 | | | | D05136J | 22 | | | ALL |
| 209B | 22 | PB | E | | 52-8 | 21-51-22 | D08050J | 25 | | | | D02826 | 2 | | | 050-099 |
| 209B | 22 | PB | E | | 62-9 | 21-51-22 | D08050J | 25 | | | | D02826 | 2 | | | 150-199, 275-299 |
| 209R | 22 | PB | E | | 0-0 | 21-51-22 | D08050J | 26 | | | | D02826 | 1 | | | ALL |
| 210B | 24 | PL | B | | 5-1 | 21-51-22 | D08050J | 27 | | | | D04004P | 18 | | | ALL |
| 210R | 24 | PL | B | | 0-0 | 21-51-22 | D08050J | 28 | | | | D04004P | 19 | | | ALL |
| 211B | 24 | PL | C | | 33-6 | 21-61-51 | D04716P | 9 | | | | D08050J | 32 | | | ALL |
| 211R | 24 | PL | C | | 0-0 | 21-61-51 | D04716P | 10 | | | | D08050J | 33 | | | ALL |
| 212B | 24 | PL | D | | 48-7 | 36-21-11 | D04004P | 17 | | | | D05136J | 9 | | | 050-099 |
| 212B | 24 | PL | D | | 59-3 | 36-21-11 | D04004P | 17 | | | | D05136J | 9 | | | 150-199, 275-299 |
| 212R | 24 | PL | D | | 0-0 | 36-21-11 | D04004P | 16 | | | | D05136J | 8 | | | ALL |
| 213B | 24 | PL | F | | 50-9 | 21-52-41 | D08050J | 23 | | | | D05136J | 23 | | | 050-099 |
| 213B | 24 | PL | F | | 61-5 | 21-52-41 | D08050J | 23 | | | | D05136J | 23 | | | 150-199, 275-299 |
| 213R | 24 | PL | F | | 0-0 | 21-52-41 | D08050J | 24 | | | | D05136J | 10 | | | ALL |
| 214B | 24 | PL | G | | 50-9 | 21-52-41 | D08050J | 41 | | | | D05136J | 2 | | | 050-099 |
| 214B | 24 | PL | G | | 61-5 | 21-52-41 | D08050J | 41 | | | | D05136J | 2 | | | 150-199, 275-299 |
| 214R | 24 | PL | G | | 0-0 | 21-52-41 | D08050J | 40 | | | | D05136J | 3 | | | ALL |
| 215B | 24 | PL | AR | | 63-3 | 28-41-22 | D04804J | 24 | | | | D04418J | 11 | | | 050-099 |
| 215B | 24 | PL | AR | | 73-5 | 28-41-22 | D04804J | 24 | | | | D04418J | 11 | | | 150-199, 275-299 |
| 215R | 24 | PL | AR | | 0-0 | 28-41-22 | D04804J | 25 | | | | D04418J | 12 | | | ALL |
| 216B | 24 | PL | BA | | 63-3 | 28-41-23 | D04804J | 36 | | | | D04418J | 13 | | | 050-099 |
| 216B | 24 | PL | BA | | 73-5 | 28-41-23 | D04804J | 36 | | | | D04418J | 13 | | | 150-199, 275-299 |
| 216R | 24 | PL | BA | | 0-0 | 28-41-23 | D04804J | 37 | | | | D04418J | 14 | | | ALL |
| 217B | 24 | PW | BB | | 31-4 | 32-42-11 | D04004P | 23 | | | | D04716P | 21 | | | ALL |
| 217R | 24 | PW | BB | | 0-0 | 32-42-11 | D04004P | 24 | | | | D04716P | 20 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0730
 Page 11
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0738 | 286T0738 | | | RIGHT AIR COND PACK,ISOL VLV (continued) | | | | | | | | | | | |
| 217Z | | | | BB | 0-0 | 32-42-11 | D04004P | | 2 | | D04716P | 22 | | | ALL |
| 218B | 22 | | | PB | 62-11 | 21-52-31 | D06236P | A08 | \$D | | D05136J | 29 | | | 050-099 |
| 218B | 22 | | | PB | 73-1 | 21-52-31 | D06236P | A08 | \$D | | D05136J | 29 | | | 150-199 |
| 218B | 22 | | | PB | 73-1 | 21-52-31 | D06236P | A08 | \$D | | D05136J | 29 | | | 275-299 |
| 218R | 22 | | | PB | 0-0 | 21-52-31 | D06236P | A09 | \$D | | D05136J | 28 | | | 050-099, 150-199 |
| 218R | 22 | | | PB | 0-0 | 21-52-31 | D06236P | A09 | \$D | | D05136J | 28 | | | 275-299 |
| 219B | 22 | | | PB | 62-11 | 21-52-31 | D06236P | A18 | \$D | | D05136J | 30 | | | 050-099 |
| 219B | 22 | | | PB | 73-1 | 21-52-31 | D06236P | A18 | \$D | | D05136J | 30 | | | 150-199, 275-299 |
| 219R | 22 | | | PB | 0-0 | 21-52-31 | D06236P | A19 | \$D | | D05136J | 31 | | | ALL |
| 220B | 22 | | | PB | 62-11 | 21-52-31 | D06236P | B05 | \$D | | D05136J | 37 | | | 050-099 |
| 220B | 22 | | | PB | 73-1 | 21-52-31 | D06236P | B05 | \$D | | D05136J | 37 | | | 150-199, 275-299 |
| 220R | 22 | | | PB | 0-0 | 21-52-31 | D06236P | B06 | \$D | | D05136J | 38 | | | ALL |
| 221B | 22 | | | PB | 62-11 | 21-52-31 | D06236P | B09 | \$D | | D05136J | 39 | | | 050-099 |
| 221B | 22 | | | PB | 73-1 | 21-52-31 | D06236P | B09 | \$D | | D05136J | 39 | | | 150-199, 275-299 |
| 221R | 22 | | | PB | 0-0 | 21-52-31 | D06236P | B10 | \$D | | D05136J | 40 | | | ALL |
| 222B | 22 | | | UB | 50-9 | 21-51-22 | D08050J | 44 | | | D05136J | 33 | | | 050-099 |
| 222B | 22 | | | UB | 61-5 | 21-51-22 | D08050J | 44 | | | D05136J | 33 | | | 150-199, 275-299 |
| 222R | 22 | | | UB | 0-0 | 21-51-22 | D08050J | 43 | | | D05136J | 34 | | | ALL |
| 223B | 24 | | | PL | 37-7 | 21-52-41 | D08050J | 45 | | | D06236P | A10 | \$D | | ALL |
| 223R | 24 | | | PL | 0-0 | 21-52-41 | D08050J | 46 | | | D06236P | A11 | \$D | | ALL |
| 224B | 22 | | | PB | 62-11 | 21-52-31 | D06236P | B15 | \$D | | D05136J | 35 | | | 050-099 |
| 224B | 22 | | | PB | 73-1 | 21-52-31 | D06236P | B15 | \$D | | D05136J | 35 | | | 150-199, 275-299 |
| 224R | 22 | | | PB | 0-0 | 21-52-31 | D06236P | B16 | \$D | | D05136J | 36 | | | ALL |
| 226B | 24 | | | PW | 35-5 | 73-21-14 | D06236P | B02 | \$D | | D05266P | 3 | | | ALL |
| 226R | 24 | | | PW | 0-0 | 73-21-14 | D06236P | B03 | \$D | | D05266P | 4 | | | ALL |
| 226Z | | | | BK | 0-0 | 73-21-14 | D06236P | B04 | \$D | | D05266P | 5 | | | ALL |
| 227B | 22 | | | PB | 62-11 | 21-52-31 | D06236P | B07 | \$D | | D05136J | 1 | | | 050-099 |
| 227B | 22 | | | PB | 73-1 | 21-52-31 | D06236P | B07 | \$D | | D05136J | 1 | | | 150-199, 275-299 |
| 227R | 22 | | | PB | 0-0 | 21-52-31 | D06236P | B08 | \$D | | D05136J | 14 | | | ALL |
| 228B | 24 | | | PL | 35-5 | 36-21-11 | D04004P | 31 | | | D06236P | A17 | \$D | | 050-099 |
| 228B | 24 | | | PL | 35-5 | 36-21-11 | D04004P | 31 | | | D06236P | A17 | \$D | | 150-199, 275-299 |
| 228R | 24 | | | PL | 0-0 | 36-21-11 | D04004P | 30 | | | D06236P | A16 | \$D | | 050-099 |
| 228R | 24 | | | PL | 0-0 | 36-21-11 | D04004P | 30 | | | D06236P | A16 | \$D | | 150-199, 275-299 |
| 301B | 24 | | | PM | 50-8 | 21-53-21 | D08050J | 1 | | | D05056J | 1 | | | 050-099 |
| 301B | 24 | | | PM | 61-3 | 21-53-21 | D08050J | 1 | | | D05056J | 1 | | | 150-199, 275-299 |
| 301R | 24 | | | PM | 0-0 | 21-53-21 | D08050J | 2 | | | D05056J | 2 | | | ALL |
| 301Y | 24 | | | PM | 0-0 | 21-53-21 | D08050J | 3 | | | D05056J | 3 | | | ALL |
| 302B | 24 | | | PM | 50-8 | 21-53-21 | D08050J | 4 | | | D05056J | 4 | | | 050-099 |
| 302B | 24 | | | PM | 61-3 | 21-53-21 | D08050J | 4 | | | D05056J | 4 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0730

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0738 | 286T0738 | | | RIGHT AIR COND PACK,ISOL VLV (continued) | | | | | | | | | | | | |
| 302R | 24 | | PM | AB | 0-0 | 21-53-21 | D08050J | | | 5 | | | D05056J | | 5 | ALL |
| 302Y | 24 | | PM | AB | 0-0 | 21-53-21 | D08050J | | | 6 | | | D05056J | | 6 | ALL |
| 303B | 24 | | PM | AC | 50-8 | 21-53-21 | D08050J | | | 7 | | | D05056J | | 7 | 050-099 |
| 303B | 24 | | PM | AC | 61-3 | 21-53-21 | D08050J | | | 7 | | | D05056J | | 7 | 150-199, 275-299 |
| 303R | 24 | | PM | AC | 0-0 | 21-53-21 | D08050J | | | 8 | | | D05056J | | 8 | ALL |
| 303Y | 24 | | PM | AC | 0-0 | 21-53-21 | D08050J | | | 9 | | | D05056J | | 9 | ALL |
| 304B | 24 | | PM | AF | 62-11 | 21-52-21 | D06236P | | A02 | \$D | | | D05136J | | 4 | 050-099 |
| 304B | 24 | | PM | AF | 73-1 | 21-52-21 | D06236P | | A02 | \$D | | | D05136J | | 4 | 150-199, 275-299 |
| 304R | 24 | | PM | AF | 0-0 | 21-52-21 | D06236P | | A03 | \$D | | | D05136J | | 5 | ALL |
| 304Y | 24 | | PM | AF | 0-0 | 21-52-21 | D06236P | | A04 | \$D | | | D05136J | | 6 | ALL |
| 305B | 24 | | PM | AG | 62-10 | 21-52-21 | D06236P | | A05 | \$D | | | D05056J | | 10 | 050-099 |
| 305B | 24 | | PM | AG | 73-0 | 21-52-21 | D06236P | | A05 | \$D | | | D05056J | | 10 | 150-199, 275-299 |
| 305R | 24 | | PM | AG | 0-0 | 21-52-21 | D06236P | | A06 | \$D | | | D05056J | | 11 | ALL |
| 305Y | 24 | | PM | AG | 0-0 | 21-52-21 | D06236P | | A07 | \$D | | | D05056J | | 12 | ALL |
| 306B | 22 | | PC | AK | 50-8 | 21-51-22 | D08050J | | | 10 | | | D05056J | | 13 | 050-099 |
| 306B | 22 | | PC | AK | 61-3 | 21-51-22 | D08050J | | | 10 | | | D05056J | | 13 | 150-199, 275-299 |
| 306R | 22 | | PC | AK | 0-0 | 21-51-22 | D08050J | | | 11 | | | D05056J | | 14 | ALL |
| 306Y | 22 | | PC | AK | 0-0 | 21-51-22 | D08050J | | | 12 | | | D05056J | | 15 | ALL |
| 307B | 22 | | PC | AL | 50-8 | 21-51-22 | D08050J | | | 13 | | | D05056J | | 16 | 050-099 |
| 307B | 22 | | PC | AL | 61-3 | 21-51-22 | D08050J | | | 13 | | | D05056J | | 16 | 150-199, 275-299 |
| 307R | 22 | | PC | AL | 0-0 | 21-51-22 | D08050J | | | 14 | | | D05056J | | 17 | ALL |
| 307Y | 22 | | PC | AL | 0-0 | 21-51-22 | D08050J | | | 15 | | | D05056J | | 18 | ALL |
| 308B | 22 | | PC | AM | 50-9 | 21-51-22 | D08050J | | | 16 | | | D05136J | | 16 | 050-099 |
| 308B | 22 | | PC | AM | 61-5 | 21-51-22 | D08050J | | | 16 | | | D05136J | | 16 | 150-199, 275-299 |
| 308R | 22 | | PC | AM | 0-0 | 21-51-22 | D08050J | | | 17 | | | D05136J | | 17 | ALL |
| 308Y | 22 | | PC | AM | 0-0 | 21-51-22 | D08050J | | | 18 | | | D05136J | | 18 | ALL |
| 309B | 22 | | PC | MI | 62-10 | 21-52-21 | D06236P | | B11 | \$D | | | D05056J | | 25 | 050-099 |
| 309B | 22 | | PC | MI | 73-0 | 21-52-21 | D06236P | | B11 | | | | D05056J | | 25 | 150-199 |
| 309B | 22 | | PC | MI | 73-0 | 21-52-21 | D06236P | | B11 | \$D | | | D05056J | | 25 | 275-299 |
| 309R | 22 | | PC | MI | 0-0 | 21-52-21 | D06236P | | B12 | \$D | | | D05056J | | 26 | 050-099, 275-299 |
| 309R | 22 | | PC | MI | 0-0 | 21-52-21 | D06236P | | B12 | | | | D05056J | | 26 | 150-199 |
| 309Y | 22 | | PC | MI | 0-0 | 21-52-21 | D06236P | | B13 | \$D | | | D05056J | | 27 | 050-099, 275-299 |
| 309Y | 22 | | PC | MI | 0-0 | 21-52-21 | D06236P | | B13 | | | | D05056J | | 27 | 150-199 |
| 401B | 24 | | PN | AP | 50-9 | 21-52-41 | D08050J | | | 39 | | | D05136J | | 24 | 050-099 |
| 401B | 24 | | PN | AP | 61-5 | 21-52-41 | D08050J | | | 39 | | | D05136J | | 24 | 150-199, 275-299 |
| 401G | 24 | | PN | AP | 0-0 | 21-52-41 | D08050J | | | 36 | | | D05136J | | 25 | ALL |
| 401R | 24 | | PN | AP | 0-0 | 21-52-41 | D08050J | | | 37 | | | D05136J | | 26 | ALL |
| 401Y | 24 | | PN | AP | 0-0 | 21-52-41 | D08050J | | | 38 | | | D05136J | | 27 | ALL |

WIRE LIST

D280T132

91-21-11
Section W0730
Page 13
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0738 | 286T0738 | | | RIGHT AIR COND PACK,ISOL VLV (continued) | | | | | | | | | | | | | |
| 508 | 22 | | PA | 31-4 | 21-45-22 | D04716P | | 3 | | | | | D05266P | 7 | | | 050-099, 155-199, 276-299 |
| 508 | 22 | | PA | 31-4 | 21-45-22 | D05266P | | 7 | | | | | D04716P | 3 | | | 150-154, 275 |
| 510 | 20 | | PA | 31-4 | 25-31-11 | D05266P | | 23 | | | | | D04716P | 29 | | | 277-278 |
| 510 | 18 | | PA | 31-4 | 25-31-11 | D05266P | | 23 | DK | | | | D04716P | 29 | DK | | 280-299 |
| 511 | 20 | | PA | 91-11 | 27-18-11 | D06968P | | 1 | | | | | SP02630 | | 9 | | 155-157, 166-199, 277-299 |
| 512 | 20 | | PA | 91-11 | 27-18-11 | D06968P | | 2 | | | | | SP02634 | | 9 | | 155-157, 166-199, 277-299 |
| 513 | 20 | | PA | 91-11 | 27-18-11 | D06968P | | 3 | | | | | SP05086 | | 9 | | 155-157, 166-199, 277-299 |
| 514 | 20 | | PA | 91-11 | 27-18-11 | D06968P | | 4 | | | | | D06978J | | 1 | | 155-157, 166-199, 277-299 |
| 515 | 20 | | PA | 91-11 | 27-18-11 | D06968P | | 5 | | | | | D06978J | | 2 | | 155-157, 166-199, 277-299 |
| 516 | 20 | | PA | 91-11 | 27-18-11 | D06968P | | 6 | | | | | D06978J | | 3 | | 155-157, 166-199, 277-299 |
| 517 | 20 | | PA | 31-4 | SPARE | D05266P | | 19 | | | | | D04716P | | 30 | | 280-299 |
| 518 | 18 | | PA | 31-4 | 38-32-11 | D04716P | | 4 | DK | | | | D04004P | | 1 | DL | 275-276 |
| 801 | 22 | | PA | 48-6 | SPARE | D04004P | | 5 | | | | | D05056J | | 24 | | 050-099 |
| 801 | 22 | | PA | 59-1 | SPARE | D04004P | | 5 | | | | | D05056J | | 24 | | 150-199, 275-299 |
| 802 | 20 | | PA | 63-3 | SPARE | D04804J | | 41 | | | | | D04538J | | 3 | | 050-099 |
| 802 | 20 | | PA | 73-4 | SPARE | D04804J | | 41 | | | | | D04538J | | 3 | | 150-199, 275-299 |
| 803 | 22 | | PA | 65-8 | SPARE | D05230J | | 9 | | | | | D04268J | | 17 | | 050-099 |
| 803 | 22 | | PA | 75-10 | SPARE | D05230J | | 9 | | | | | D04268J | | 17 | | 150-199, 275-299 |
| 816 | 24 | | PK | 0-7 | SPARE | D06236P | | | B17 | \$D | | | D06236P | | CAP | Y | ALL |
| 817 | 24 | | PK | 0-7 | SPARE | D06236P | | | B18 | \$D | | | D06236P | | CAP | Y | ALL |
| 818 | 24 | | PK | 0-7 | SPARE | D06236P | | | B19 | \$D | | | D06236P | | CAP | Y | ALL |
| A-A | | | | 0-0 | 27-18-11 | M01148 | | | B | | | | SP02630 | | 9 | | 155-157, 166-199, 277-299 |
| A-B | | | | 0-0 | 27-18-11 | M01149 | | | B | | | | SP02634 | | 9 | | 155-157, 166-199, 277-299 |
| FRA | | | | 0-0 | 78-34-21 | D05266P | | | | | FA | | D05266P | | 9 | | ALL |
| FRB | | | | 0-0 | 78-34-21 | D04716P | | | | | FB | | D04716P | | 17 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0730

Page 14 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0741 | 286T0741 | | | YAW DAMPER, SHELF TO AC1305 | | | | | | | | | | | |
| 101 | 22 | | PA | | 145-0 | 22-21-11 | D04981P | | | | D01937 | | | | 150-199, 275-299 |
| 102 | 22 | | PA | | 145-0 | 22-21-11 | D04981P | | | | D01937 | | | | 150-199, 275-299 |
| 201B | 22 | | PB | IA | 145-0 | 22-21-11 | D04981P | | | | D01937 | | | | 150-199, 275-299 |
| 201R | 22 | | PB | IA | 0-0 | 22-21-11 | D04981P | | | | D01937 | | | | 150-199, 275-299 |
| 202B | 22 | | PR | IB | 145-0 | 22-21-11 | D04981P | | | | D01937 | | | | 150-199, 275-299 |
| 202R | 22 | | PR | IB | 0-0 | 22-21-11 | D04981P | | | | D01937 | | | | 150-199, 275-299 |
| 202Z | | | | IB | 0-0 | 22-21-11 | D04981P | | | | D01937 | DED | | | 150-199, 275-299 |
| W0743 | 286T0743 | | | YAW DAMPER, SHELF TO ACCELEROMETER, R | | | | | | | | | | | |
| 101 | 22 | | PA | | 128-0 | 22-21-21 | D04983P | | | | D01939 | | | | 150-199, 275-299 |
| 102 | 22 | | PA | | 128-0 | 22-21-21 | D04983P | | | | D01939 | | | | 150-199, 275-299 |
| 201B | 22 | | PB | IA | 128-0 | 22-21-21 | D04983P | | | | D01939 | | | | 150-199, 275-299 |
| 201R | 22 | | PB | IA | 0-0 | 22-21-21 | D04983P | | | | D01939 | | | | 150-199, 275-299 |
| 202B | 22 | | PR | IB | 128-0 | 22-21-21 | D04983P | | | | D01939 | | | | 150-199, 275-299 |
| 202R | 22 | | PR | IB | 0-0 | 22-21-21 | D04983P | | | | D01939 | | | | 150-199, 275-299 |
| 202Z | | | | IB | 0-0 | 22-21-21 | D04983P | | | | D01939 | DED | | | 150-199, 275-299 |
| W0744 | 286T0744 | | | P61 TO L WING FS - L2B- FLT CONT & ENG INSTR | | | | | | | | | | | |
| 002 | 24 | | PK | | 53-0 | 73-34-11 | D06240P | A11 | \$D | | D04524J | | | | 050-099 |
| 002 | 24 | | PK | | 65-0 | 73-34-11 | D04524J | | | | D06240P | A11 | \$D | | 150-199, 275-299 |
| 003 | 22 | | PA | | 79-8 | SPARE | D04524J | | | | D04720P | | | | 050-099 |
| 003 | 22 | | PA | | 89-4 | SPARE | D04524J | | | | D04720P | | | | 150-199, 275-299 |
| 004 | 22 | | PA | | 79-8 | SPARE | D04524J | | | | D04720P | | | | 050-099 |
| 004 | 22 | | PA | | 89-4 | SPARE | D04524J | | | | D04720P | | | | 150-199, 275-299 |
| 006 | 22 | | PA | | 79-8 | SPARE | D04524J | | | | D04720P | | | | 050-099 |
| 007 | 24 | | PK | | 79-8 | SPARE | D04524J | | | | D04720P | | | | 050-099 |
| 008 | 24 | | PK | | 79-8 | SPARE | D04524J | | | | D04720P | | | | 050-099 |
| 009 | 22 | | PA | | 79-8 | 29-11-11 | D04524J | | | | D04720P | | | | 050-099 |
| 009 | 22 | | PA | | 89-4 | 29-11-11 | D04524J | | | | D04720P | | | | 150-199, 275-299 |
| 012 | 22 | | PA | | 50-0 | 74-31-11 | D04524J | | | | D05308P | | | | 050-099 |
| 012 | 22 | | PA | | 62-0 | 74-31-11 | D04524J | | | | D05308P | | | | 150-199, 275-299 |
| 014 | 18 | | PA | | 50-0 | 36-11-61 | D05308P | | | | D04524J | 42 | DK | | 050-099 |
| 014 | 18 | | PA | | 62-0 | 36-11-61 | D05308P | | | | D04524J | 42 | DK | | 150-199, 275-299 |
| 023 | 18 | | PA | | 50-0 | 36-11-61 | D05308P | | | | D04524J | 43 | DK | | 050-099 |
| 023 | 18 | | PA | | 62-0 | 36-11-61 | D05308P | | | | D04524J | 43 | DK | | 150-199, 275-299 |
| 025 | 20 | | PA | | 62-0 | SPARE | D04524J | | | | D05308P | | | | 150-199, 275-299 |
| 026 | 22 | | PA | | 35-3 | 27-23-11 | D04720P | | | | D05308P | | | | ALL |
| 027 | 22 | | PA | | 35-3 | 74-31-11 | D04720P | | | | D05308P | | | | ALL |
| 028 | 18 | | PA | | 35-3 | 27-23-11 | D04720P | | | | D05308P | 21 | DK | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0740

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0744 | 286T0744 | | | P61 TO L WING FS - L2B- FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | |
| 029 | 18 | PA | | 35-3 | 27-23-11 | D04720P | 23 | DL | | D05308P | 23 | DK | | ALL | | |
| 036 | 20 | PA | | 79-8 | SPARE | D04524J | 21 | | | D04720P | 33 | | | 050-099 | | |
| 036 | 20 | PA | | 89-4 | SPARE | D04524J | 21 | | | D04720P | 33 | | | 150-199, 275-299 | | |
| 037 | 20 | PA | | 79-8 | SPARE | D04524J | 22 | | | D04720P | 34 | | | 050-099 | | |
| 037 | 20 | PA | | 89-4 | SPARE | D04524J | 22 | | | D04720P | 34 | | | 150-199, 275-299 | | |
| 039 | 22 | PA | | 35-3 | 74-31-11 | D04720P | 28 | | | D05308P | 13 | | | ALL | | |
| 040 | 22 | PA | | 35-3 | 74-31-11 | D04720P | 29 | | | D05308P | 14 | | | ALL | | |
| 042 | 22 | PA | | 41-10 | 31-41-11 | D06254P | 1 | | | D04720P | 9 | | | ALL | | |
| 043 | 24 | PK | | 50-0 | 36-11-61 | D05308P | 41 | | | D04524J | 44 | | | 050-099 | | |
| 043 | 24 | PK | | 62-0 | 36-11-61 | D05308P | 41 | | | D04524J | 44 | | | 150-199, 275-299 | | |
| 044 | 24 | PK | | 41-11 | 79-32-11 | D04720P | 14 | | | D06240P | A10 | \$D | | ALL | | |
| 046 | 24 | PK | | 1-0 | SPARE | D06240P | A12 | \$D | | D06240P | CAP | Y | | 275-299 | | |
| 049 | 24 | PK | | 1-0 | SPARE | D06240P | A14 | \$D | | D06240P | CAP | Y | | 050-099 | | |
| 051 | 24 | PK | | 1-0 | SPARE | D06240P | A13 | \$D | | D06240P | CAP | Y | | 275-299 | | |
| 052 | 24 | PK | | 12-0 | 76-11-11 | D06240P | A17 | \$D | | D05308P | 1 | | | ALL | | |
| 053 | 24 | PK | | 1-0 | SPARE | D06240P | A18 | \$D | | D06240P | CAP | Y | | 150-199, 275-299 | | |
| 054 | 24 | PK | | 1-0 | SPARE | D06240P | A19 | \$D | | D06240P | CAP | Y | | 150-199, 275-299 | | |
| 055 | 18 | PA | | 14-8 | 32-35-11 | D06184J | 1 | DK | | D04720P | 3 | DL | | ALL | | |
| 059 | 24 | PK | | 12-0 | 73-33-11 | D05308P | 15 | | | D06240P | A15 | \$D | | 050-099 | | |
| 059 | 24 | PK | | 12-0 | 73-33-11 | D06240P | A15 | \$D | | D05308P | 15 | | | 150-199, 275-299 | | |
| 060 | 24 | PK | | 89-4 | SPARE | D04524J | 7 | | | D04720P | 6 | | | 150-199 | | |
| 061 | 24 | PK | | 65-0 | SPARE | D06240P | A14 | \$D | | D04524J | 8 | | | 150-199 | | |
| 063 | 24 | PK | | 11-0 | 24-25-13 | D06254P | 6 | | | D05308P | 36 | | | 050-099 | | |
| 063 | 24 | PK | | 11-0 | 24-25-13 | D05308P | 36 | | | D06254P | 6 | | | 150-199, 275-299 | | |
| 064 | 24 | PK | | 11-0 | 24-25-13 | D06254P | 7 | | | D05308P | 37 | | | 050-099 | | |
| 064 | 24 | PK | | 11-0 | 24-25-13 | D05308P | 37 | | | D06254P | 7 | | | 150-199, 275-299 | | |
| 065 | 24 | PK | | 11-0 | 24-25-13 | D06254P | 8 | | | D05308P | 38 | | | 050-099 | | |
| 065 | 24 | PK | | 11-0 | 24-25-13 | D05308P | 38 | | | D06254P | 8 | | | 150-199, 275-299 | | |
| 066 | 24 | PK | | 11-0 | 24-25-13 | D06254P | 9 | | | D05308P | 39 | | | 050-099 | | |
| 066 | 24 | PK | | 11-0 | 24-25-13 | D05308P | 39 | | | D06254P | 9 | | | 150-199, 275-299 | | |
| 077 | 20 | PA | | 1-6 | 77-35-11 | D08608 | 1 | | | GD00691 | D.. | 2 | | ALL | | |
| 091 | 16 | PQ | DP | 35-3 | SPARE | D04720P | 18 | FL | | D05308P | CAP | Y | | 050-099, 155-199 | | |
| 091Z | | | DP | 0-0 | SPARE | D04720P | 17 | | | D05308P | DED | | | 050-099, 155-166 | | |
| 091Z | | | DP | 0-0 | 73-21-11 | D04720P | 17 | | | D05308P | DED | | | 167-199 | | |
| 093 | 20 | PA | | 35-3 | 73-21-11 | D04720P | 15 | | | D05308P | 12 | | | ALL | | |
| 094 | 16 | PA | | 35-3 | 73-21-11 | D04720P | 16 | FL | | D05308P | 16 | FM | | ALL | | |
| 095 | 24 | PK | | 50-0 | 36-11-61 | D05308P | 24 | | | D04524J | 30 | | | 050-099 | | |
| 095 | 24 | PK | | 58-0 | 36-11-61 | D05308P | 24 | | | D04524J | 30 | | | 150-199, 275-299 | | |
| 096 | 24 | PK | | 50-0 | 36-11-61 | D05308P | 25 | | | D04524J | 31 | | | 050-099 | | |

WIRE LIST

D280T132

91-21-11

Section W0740

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0744 | 286T0744 | | | P61 TO L WING FS - L2B- FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | | |
| 096 | 24 | | PK | | 58-0 | 36-11-61 | D05308P | | 25 | | | | | D04524J | 31 | | | 150-199, 275-299 |
| 097 | 24 | | PK | | 50-0 | 36-11-61 | D05308P | | 26 | | | | | D04524J | 32 | | | 050-099 |
| 097 | 24 | | PK | | 58-0 | 36-11-61 | D05308P | | 26 | | | | | D04524J | 32 | | | 150-199, 275-299 |
| 104 | 18 | | PA | | 50-0 | 78-34-11 | D05308P | | 6 | DK | | | | D04524J | 18 | DK | | 050-099 |
| 104 | 18 | | PA | | 59-0 | 78-34-11 | D05308P | | 6 | DK | | | | D04524J | 18 | DK | | 150-156, 162-166, 275-276 |
| 104 | 18 | | PA | | 59-0 | SPARE | D05308P | | 6 | DK | | | | D04524J | 18 | DK | | 157, 167-199, 277-299 |
| 113 | 18 | | PQ | M | 50-0 | 78-34-11 | D05308P | | 8 | DK | | | | D04524J | 45 | DK | | 050-099 |
| 113 | 18 | | PQ | EM | 62-0 | 78-34-11 | D05308P | | 8 | DK | | | | D04524J | 45 | DK | | 150-199, 275-299 |
| 113Z | | | | M | 0-0 | 78-34-11 | D05308P | | | | | | FX | D04524J | =CC | D | | 050-099 |
| 113Z | | | | EM | 0-0 | 78-34-11 | D05308P | | | | | | FX | D04524J | =CC | D | | 150-199, 275-299 |
| 114 | 18 | | PQ | N | 50-0 | 78-34-11 | D05308P | | 22 | DK | | | | D04524J | 46 | DK | | 050-099 |
| 114 | 18 | | PQ | EN | 62-0 | 78-34-11 | D05308P | | 22 | DK | | | | D04524J | 46 | DK | | 150-199, 275-299 |
| 114Z | | | | N | 0-0 | 78-34-11 | D05308P | | | | | | FX | D04524J | =CC | D | | 050-099 |
| 114Z | | | | EN | 0-0 | 78-34-11 | D05308P | | | | | | FX | D04524J | =CC | D | | 150-199, 275-299 |
| 115 | 18 | | PQ | AB | 50-0 | 78-34-11 | D05308P | | 18 | DK | | | | D04524J | 33 | DK | | 050-099 |
| 115 | 18 | | PQ | EO | 62-0 | 78-34-11 | D05308P | | 18 | DK | | | | D04524J | 33 | DK | | 150-199, 275-299 |
| 115Z | | | | AB | 0-0 | 78-34-11 | D05308P | | | | | | FX | D04524J | =CC | D | | 050-099 |
| 115Z | | | | EO | 0-0 | 78-34-11 | D05308P | | | | | | FX | D04524J | =CC | D | | 150-199, 275-299 |
| 116 | 18 | | PQ | AK | 50-0 | 78-34-11 | D05308P | | 19 | DK | | | | D04524J | 47 | DK | | 050-099 |
| 116 | 18 | | PQ | EP | 62-0 | 78-34-11 | D05308P | | 19 | DK | | | | D04524J | 47 | DK | | 150-199, 275-299 |
| 116Z | | | | AK | 0-0 | 78-34-11 | D05308P | | | | | | FX | D04524J | =CC | D | | 050-099 |
| 116Z | | | | EP | 0-0 | 78-34-11 | D05308P | | | | | | FX | D04524J | =CC | D | | 150-199, 275-299 |
| 117 | 18 | | PQ | AL | 50-0 | 78-34-11 | D05308P | | 35 | DK | | | | D04524J | 48 | DK | | 050-099 |
| 117 | 18 | | PQ | EQ | 62-0 | 78-34-11 | D05308P | | 35 | DK | | | | D04524J | 48 | DK | | 150-199, 275-299 |
| 117Z | | | | AL | 0-0 | 78-34-11 | D05308P | | | | | | FX | D04524J | =CC | D | | 050-099 |
| 117Z | | | | EQ | 0-0 | 78-34-11 | D05308P | | | | | | FX | D04524J | =CC | D | | 150-199, 275-299 |
| 200 | 20 | | PA | | 1-6 | 77-35-11 | D08608 | | | | | | FB | GD00691 | S.. | 2 | | 051-099 |
| 200 | 20 | | PA | | 1-6 | 77-35-11 | D08608 | | | | | | FK | GD00691 | S.. | 2 | | 150-199, 275-299 |
| 200B | 24 | | PW | HY | 40-0 | 77-35-11 | D08608 | | 9 | | | | | D08020J | 14 | | | 050-099 |
| 200B | 24 | | PW | HY | 41-0 | 77-35-11 | D08608 | | 9 | | | | | D08020J | 14 | | | 150-199, 275-299 |
| 200R | 24 | | PW | HY | 0-0 | 77-35-11 | D08608 | | 8 | | | | | D08020J | 13 | | | ALL |
| 200Z | | | | HY | 0-0 | 77-35-11 | GD00691 | | S.. | 2 | | | | D08020J | 10 | | | 050 |
| 200Z | | | | HY | 0-0 | 77-35-11 | D08608 | | | | | | FB | D08020J | 10 | | | 051-099 |
| 200Z | | | | HY | 0-0 | 77-35-11 | D08608 | | | | | | FK | D08020J | 10 | | | 150-199, 275-299 |
| 201B | 24 | | PL | IA | 50-0 | 78-34-11 | D08020J | | 1 | | | | | D04524J | 23 | | | 050-099 |
| 201B | 24 | | PL | B | 62-0 | 78-34-11 | D04524J | | 23 | | | | | D08020J | 1 | | | 150-199, 275-299 |
| 201R | 24 | | PL | IA | 0-0 | 78-34-11 | D08020J | | 2 | | | | | D04524J | 24 | | | 050-099 |
| 201R | 24 | | PL | B | 0-0 | 78-34-11 | D04524J | | 24 | | | | | D08020J | 2 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0740

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0744 | 286T0744 | | | P61 TO L WING FS - L2B- FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | |
| 202B | 24 | PL | IB | 50-0 | 78-34-11 | D08020J | | 3 | | | | | D04524J | 25 | | | 050-099 |
| 202B | 24 | PL | C | 62-0 | 78-34-11 | D04524J | | 25 | | | | | D08020J | 3 | | | 150-199, 275-299 |
| 202R | 24 | PL | IB | 0-0 | 78-34-11 | D08020J | | 4 | | | | | D04524J | 26 | | | 050-099 |
| 202R | 24 | PL | C | 0-0 | 78-34-11 | D04524J | | 26 | | | | | D08020J | 4 | | | 150-199, 275-299 |
| 204B | 24 | PW | ID | 40-0 | 73-21-14 | D08608 | | 12 | | | | | D08020J | 18 | | | 050-099 |
| 204B | 24 | PW | ID | 41-0 | 73-21-14 | D08608 | | 12 | | | | | D08020J | 18 | | | 150-199, 277-299 |
| 204F | 20 | UA | | 1-6 | 73-21-14 | D08608 | | | | | | ID | GD00691 | S.. | 2 | | 050-099 |
| 204F | 20 | PA | | 1-6 | 73-21-14 | D08608 | | | | | | ID | GD00691 | S.. | 2 | | 150-199, 277-299 |
| 204R | 24 | PW | ID | 0-0 | 73-21-14 | D08608 | | 11 | | | | | D08020J | 17 | | | 050-099, 150-199, 277-299 |
| 204Z | | | ID | 0-0 | 73-21-14 | D08608 | | | | | | ID | D08020J | 19 | | | 050-099, 150-199, 277-299 |
| 207B | 24 | PL | H | 35-3 | SPARE | D04720P | | 19 | | | | | D05308P | CAP | Y | | 050-099 |
| 207B | 24 | PL | H | 35-3 | SPARE | D04720P | | 19 | | | | | D05308P | 34 | | | 150-199, 275-299 |
| 207R | 24 | PL | H | 0-0 | SPARE | D04720P | | 20 | | | | | D05308P | CAP | Y | | 050-099 |
| 207R | 24 | PL | H | 0-0 | SPARE | D04720P | | 20 | | | | | D05308P | 9 | | | 150-199, 275-299 |
| 210B | 24 | PW | L | 37-0 | 73-21-14 | D06184J | | 11 | | | | | D05308P | 27 | | | ALL |
| 210R | 24 | PW | L | 0-0 | 73-21-14 | D06184J | | 12 | | | | | D05308P | 28 | | | ALL |
| 210Z | | | L | 0-0 | 73-21-14 | D06184J | | 13 | | | | | D05308P | 17 | | | ALL |
| 211B | 24 | PW | E | 50-0 | SPARE | D05308P | | 34 | | | | | D04524J | 38 | | | 050-099 |
| 211R | 24 | PW | E | 0-0 | SPARE | D05308P | | 9 | | | | | D04524J | 37 | | | 050-099 |
| 211Z | | | E | 0-0 | SPARE | D05308P | | 7 | | | | | D04524J | 39 | | | 050-099 |
| 212 | 20 | PA | | 1-6 | 77-35-11 | D08608 | | | | | | FC | GD00691 | S.. | 2 | | 051-099 |
| 212 | 20 | PA | | 1-6 | 77-35-11 | D08608 | | | | | | FG | GD00691 | S.. | 2 | | 150-199, 275-299 |
| 212B | 24 | PW | IL | 40-0 | 77-35-11 | D08608 | | 6 | | | | | D08020J | 16 | | | 050-099 |
| 212B | 24 | PW | IL | 41-0 | 77-35-11 | D08608 | | 6 | | | | | D08020J | 16 | | | 150-199, 275-299 |
| 212R | 24 | PW | IL | 0-0 | 77-35-11 | D08608 | | 5 | | | | | D08020J | 15 | | | ALL |
| 212Z | | | IL | 0-0 | 77-35-11 | GD00691 | | S.. | 2 | | | | D08020J | 11 | | | 050 |
| 212Z | | | IL | 0-0 | 77-35-11 | D08608 | | | | | | FC | D08020J | 11 | | | 051-099 |
| 212Z | | | IL | 0-0 | 77-35-11 | D08608 | | | | | | FG | D08020J | 11 | | | 150-199, 275-299 |
| 221B | 24 | PW | IU | 12-0 | 77-12-11 | D05308P | | 4 | | | | | D08020J | 8 | | | 050-099 |
| 221B | 24 | PW | IU | 11-0 | 77-12-11 | D05308P | | 4 | | | | | D08020J | 8 | | | 162-199, 277-299 |
| 221R | 24 | PW | IU | 0-0 | 77-12-11 | D05308P | | 5 | | | | | D08020J | 7 | | | 050-099, 162-199, 277-299 |
| 221Z | | | IU | 0-0 | 77-12-11 | D05308P | | 3 | | | | | D08020J | 9 | | | 050-099, 162-199, 277-299 |
| 302B | 24 | PX | G | 12-0 | 73-31-11 | D05308P | | 31 | | | | | D06240P | A03 | \$D | | 050-099 |
| 302B | 24 | PX | MB | 12-0 | 73-31-11 | D06240P | | A03 | \$D | | | | D05308P | 31 | | | 150-199, 275-299 |
| 302R | 24 | PX | G | 0-0 | 73-31-11 | D05308P | | 30 | | | | | D06240P | A02 | \$D | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0740

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0744 | 286T0744 | | | P61 TO L WING FS - L2B- FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 302R | 24 | PX | | MB | 0-0 | 73-31-11 | D06240P | A02 | \$D | | D05308P | 30 | | | 150-199, 275-299 |
| 302Y | 24 | PX | | G | 0-0 | 73-31-11 | D05308P | 32 | | | D06240P | A04 | \$D | | 050-099 |
| 302Y | 24 | PX | | MB | 0-0 | 73-31-11 | D06240P | A04 | \$D | | D05308P | 32 | | | 150-199, 275-299 |
| 302Z | | | | G | 0-0 | 73-31-11 | D05308P | 29 | | | D06240P | A16 | \$D | | 050-099 |
| 302Z | | | | MB | 0-0 | 73-31-11 | D06240P | A16 | \$D | | D05308P | 29 | | | 150-199, 275-299 |
| 303B | 24 | PM | | Q | 53-0 | 79-32-11 | D04524J | 15 | | | D06240P | A06 | \$D | | 050-099 |
| 303B | 24 | PM | | MC | 65-0 | 79-32-11 | D06240P | A06 | \$D | | D04524J | 15 | | | 150-199, 275-299 |
| 303R | 24 | PM | | Q | 0-0 | 79-32-11 | D04524J | 13 | | | D06240P | A07 | \$D | | 050-099 |
| 303R | 24 | PM | | MC | 0-0 | 79-32-11 | D06240P | A07 | \$D | | D04524J | 13 | | | 150-199, 275-299 |
| 303Y | 24 | PM | | Q | 0-0 | 79-32-11 | D04524J | 14 | | | D06240P | A05 | \$D | | 050-099 |
| 303Y | 24 | PM | | MC | 0-0 | 79-32-11 | D06240P | A05 | \$D | | D04524J | 14 | | | 150-199, 275-299 |
| 514 | 20 | PA | | | 5-0 | 78-34-11 | D05308P | | | FX | GD00670 | S.. | 2 | | ALL |
| FRX | | | | | 0-0 | 78-34-11 | D05308P | 33 | | | D05308P | | | FX | ALL |
| W0746 | 286T0746 | | | P61 TO L WING FS -L2A- FLT CONT & ENG INSTR | | | | | | | | | | | |
| 001 | 22 | PA | | | 49-0 | 30-21-11 | D05306P | 25 | | | D04482J | 1 | | | 050-099 |
| 001 | 22 | PA | | | 59-0 | 30-21-11 | D04482J | 1 | | | D05306P | 25 | | | 150-199, 275-299 |
| 002 | 22 | PQ | AB | | 49-0 | 78-36-11 | D05306P | 9 | | | D04482J | 9 | | | 050-099 |
| 002 | 22 | PQ | T | | 59-0 | 78-36-11 | D04482J | 9 | | | D05306P | 9 | | | 150-199 |
| 002 | 22 | PQ | AB | | 59-0 | 78-36-11 | D04482J | 9 | | | D05306P | 9 | | | 275-299 |
| 002Z | | | AB | | 0-0 | 78-36-11 | D05306P | 10 | | | D04482J | =CC | D | | 050-099 |
| 002Z | | | T | | 0-0 | 78-36-11 | D04482J | =CC | M | | D05306P | 10 | | | 150-199 |
| 002Z | | | AB | | 0-0 | 78-36-11 | D04482J | =CC | D | | D05306P | 10 | | | 275-299 |
| 005 | 22 | PA | | | 49-0 | 74-31-11 | D05306P | 7 | | | D04482J | 5 | | | 050-099 |
| 005 | 22 | PA | | | 59-0 | 74-31-11 | D04482J | 5 | | | D05306P | 7 | | | 150-199, 275-299 |
| 006 | 22 | PA | | | 49-0 | 79-35-11 | D05306P | 44 | | | D04482J | 6 | | | 050-099 |
| 006 | 22 | PA | | | 59-0 | 79-35-11 | D04482J | 6 | | | D05306P | 44 | | | 150-199, 275-299 |
| 007 | 24 | PK | | | 34-0 | 75-23-11 | D04732P | 20 | | | SM00001 | | 9 | | 050-099 |
| 007 | 24 | PK | | | 34-0 | 75-23-11 | SM00001 | | 9 | | D04732P | 20 | | | 150-199, 275-299 |
| 009 | 20 | PA | | | 59-0 | SPARE | D04482J | 18 | | | D05306P | 18 | | | 150-156, 162-199 |
| 009 | 20 | PA | | | 59-0 | SPARE | D04482J | 18 | | | D05306P | CAP | Y | | 157 |
| 009 | 20 | PA | | | 59-0 | SPARE | D04482J | 16 | | | D05306P | 17 | | | 275-299 |
| 010 | 24 | PK | | | 47-0 | 73-21-14 | D06186J | 20 | | | D05306P | 48 | | | ALL |
| 011 | 24 | PK | | | 49-0 | 30-21-11 | D05306P | 26 | | | D04482J | 14 | | | 050-099 |
| 011 | 24 | PK | | | 59-0 | 30-21-11 | D04482J | 14 | | | D05306P | 26 | | | 150-199, 275-299 |
| 012 | 22 | PA | | | 49-0 | 30-21-11 | D05306P | 28 | | | D04482J | 15 | | | 050-099 |
| 012 | 22 | PA | | | 59-0 | 30-21-11 | D04482J | 15 | | | D05306P | 28 | | | 150-199, 275-299 |
| 014 | 22 | PA | | | 49-0 | 79-33-11 | D05306P | 43 | | | D04482J | 17 | | | 050-099 |
| 014 | 22 | PA | | | 59-0 | 79-33-11 | D04482J | 17 | | | D05306P | 43 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11
Section W0740
Page 5
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|---|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0746 | 286T0746 | | | P61 TO L WING FS -L2A- FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | | |
| 01TI | | | | C | 0-0 | 77-31-11 | D08022J | | 3 | | | | | D04482J | 29 | | | 050-099 |
| 01TI | | | | C | 0-0 | 77-31-11 | D04482J | | 29 | | | | | D08022J | 3 | | | 155-199, 277-299 |
| 01TO | | | | C | 0-0 | 77-31-11 | D08022J | | = CC | D | | | | D04482J | = CC | D | | 050-099 |
| 01TO | | | | C | 0-0 | 77-31-11 | D04482J | | = CC | M | | | | D08022J | = CC | M | | 155-199, 277-299 |
| 01TR | 20 | | RQ | C | 46-0 | 77-31-11 | D08022J | | 1 | | | | | D04482J | 27 | | | 050-099 |
| 01TR | 20 | | RQ | C | 57-0 | 77-31-11 | D04482J | | 27 | | | | | D08022J | 1 | | | 155-199 |
| 01TR | 20 | | RQ | C | 56-0 | 77-31-11 | D04482J | | 27 | | | | | D08022J | 1 | | | 277-299 |
| 01TW | 20 | | RQ | C | 0-0 | 77-31-11 | D08022J | | 2 | | | | | D04482J | 28 | | | 050-099 |
| 01TW | 20 | | RQ | C | 0-0 | 77-31-11 | D04482J | | 28 | | | | | D08022J | 2 | | | 155-199, 277-299 |
| 020 | 24 | | PK | | 49-0 | 78-34-11 | D05306P | | 19 | | | | | D04482J | 38 | | | 050-099 |
| 020 | 24 | | PK | | 59-0 | 78-34-11 | D04482J | | 38 | | | | | D05306P | 19 | | | 150-199, 275-299 |
| 022 | 22 | | PA | | 77-0 | SPARE | D04732P | | 27 | | | | | D04482J | 42 | | | 050-099 |
| 022 | 22 | | PA | | 87-0 | SPARE | D04482J | | 42 | | | | | D04732P | 27 | | | 150-199, 275-299 |
| 023 | 18 | | PA | | 36-0 | 27-23-11 | D05306P | | 1 | DK | | | | D04730P | 1 | | | ALL |
| 024 | 18 | | PA | | 36-0 | 27-23-11 | D05306P | | 15 | DK | | | | D04730P | 2 | | | ALL |
| 025 | 22 | | PA | | 36-0 | 27-23-11 | D05306P | | 16 | | | | | D04730P | 3 | | | ALL |
| 026 | 20 | | PA | | 36-0 | 27-13-11 | D05306P | | 22 | | | | | D04730P | 4 | | | ALL |
| 027 | 20 | | PA | | 36-0 | 27-13-11 | D05306P | | 27 | | | | | D04730P | 5 | | | ALL |
| 028 | 22 | | PA | | 36-0 | 27-13-11 | D05306P | | 21 | | | | | D04730P | 6 | | | ALL |
| 029 | 24 | | PK | | 39-0 | 78-36-11 | D04732P | | 10 | | | | | D08022J | 15 | | | ALL |
| 039 | 24 | | PK | | 36-0 | SPARE | D04730P | | 7 | | | | | D05306P | CAP | Y | | ALL |
| 040 | 24 | | PK | | 36-0 | 26-18-11 | D04730P | | 8 | | | | | D05306P | 30 | | | ALL |
| 041 | 24 | | PK | | 49-0 | 30-21-11 | D05306P | | 32 | | | | | D04482J | 41 | | | 050-099 |
| 041 | 24 | | PK | | 59-0 | 30-21-11 | D05306P | | 32 | | | | | D04482J | 41 | | | 150-199, 275-299 |
| 043 | 24 | | PK | | 49-0 | 78-36-11 | D05306P | | 38 | | | | | D04482J | 40 | | | 050-099 |
| 043 | 24 | | PK | | 59-0 | 78-36-11 | D04482J | | 40 | | | | | D05306P | 38 | | | 150-199, 275-299 |
| 044 | 24 | | PK | | 49-0 | SPARE | D05306P | | 37 | | | | | D04482J | 13 | | | 050-099 |
| 044 | 24 | | PK | | 59-0 | SPARE | D04482J | | 13 | | | | | D05306P | 37 | | | 150-199 |
| 044 | 24 | | PK | | 59-0 | SPARE | D05306P | | 37 | | | | | D04482J | 13 | | | 275-299 |
| 045 | 22 | | PA | | 35-0 | 74-31-11 | D04732P | | 4 | | | | | D05306P | 45 | | | ALL |
| 046 | 22 | | PA | | 35-0 | 74-31-11 | D04732P | | 5 | | | | | D05306P | 20 | | | ALL |
| 047 | 22 | | PA | | 35-0 | 74-31-11 | D04732P | | 6 | | | | | D05306P | 3 | | | ALL |
| 048 | 24 | | PK | | 15-0 | 27-58-11 | D04732P | | 33 | | | | | D06186J | 17 | | | ALL |
| 049 | 24 | | PK | | 15-0 | 27-58-11 | D04732P | | 32 | | | | | D06186J | 16 | | | ALL |
| 050 | 24 | | PK | | 15-0 | 27-58-11 | D04732P | | 31 | | | | | D06186J | 15 | | | ALL |
| 051 | 24 | | PK | | 15-0 | 27-58-11 | D04732P | | 30 | | | | | D06186J | 14 | | | ALL |
| 052 | 24 | | PK | | 15-0 | 27-58-11 | D04732P | | 29 | | | | | D06186J | 13 | | | ALL |
| 053 | 24 | | PK | | 15-0 | 27-58-11 | D04732P | | 28 | | | | | D06186J | 12 | | | ALL |
| 054 | 24 | | PK | | 15-0 | 27-51-11 | D06186J | | 11 | | | | | D04732P | 7 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0740

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0746 | 286T0746 | | | P61 TO L WING FS -L2A- FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 055 | 22 | | PA | 15-0 | 27-58-31 | D06186J | | 18 | | D04732P | | 8 | | | ALL |
| 056 | 22 | | PA | 15-0 | 27-88-11 | D04730P | | 9 | | D06186J | | 19 | | | ALL |
| 057 | 22 | | PA | 44-0 | 79-33-11 | D06186J | | 10 | | D05306P | | 42 | | | ALL |
| 058 | 22 | | PA | 15-0 | 32-46-11 | D06186J | | 1 | | D04732P | | 19 | | | ALL |
| 059 | 24 | | PK | 48-0 | 32-61-14 | D06186J | | 2 | | D08022J | | 18 | | | ALL |
| 060 | 24 | | PK | 48-0 | 32-61-14 | D06186J | | 3 | | D08022J | | 19 | | | ALL |
| 061 | 24 | | PK | 48-0 | 32-61-14 | D06186J | | 4 | | D08022J | | 20 | | | ALL |
| 062 | 24 | | PK | 48-0 | 32-61-14 | D06186J | | 5 | | D08022J | | 21 | | | ALL |
| 063 | 24 | | PK | 48-0 | 32-61-14 | D06186J | | 6 | | D08022J | | 22 | | | ALL |
| 064 | 22 | | PA | 48-0 | SPARE | D06186J | | 7 | | D08022J | CAP | Y | | | 150-199, 275-299 |
| 065 | 24 | | PK | 49-0 | 75-23-11 | D05306P | | 2 | | D04482J | | 12 | | | 050-099 |
| 065 | 24 | | PK | 59-0 | 75-23-11 | D05306P | | 2 | | D04482J | | 12 | | | 150-199, 275-299 |
| 066 | 24 | | PK | 49-0 | 75-23-11 | D05306P | | 4 | | D04482J | | 50 | | | 050-099 |
| 066 | 24 | | PK | 59-0 | 75-23-11 | D05306P | | 4 | | D04482J | | 50 | | | 150-199, 275-299 |
| 067 | 24 | | PK | 6-0 | 75-23-11 | D05306P | | 5 | | SM00001 | | 9 | | | ALL |
| 068 | 24 | | PK | 49-0 | 75-23-11 | D05306P | | 6 | | D04482J | | 51 | | | 050-099 |
| 068 | 24 | | PK | 59-0 | 75-23-11 | D05306P | | 6 | | D04482J | | 51 | | | 150-199, 275-299 |
| 069 | 24 | | PK | 44-0 | 75-23-11 | D04482J | | 7 | | SM00001 | | 9 | | | 050-099 |
| 069 | 24 | | PK | 56-0 | 75-23-11 | D04482J | | 7 | | SM00001 | | 9 | | | 150-199, 275-299 |
| 071 | 24 | | PK | 77-0 | 73-33-11 | D04732P | | 3 | | D04482J | | 47 | | | 050-099 |
| 071 | 24 | | PK | 87-0 | 73-33-11 | D04732P | | 3 | | D04482J | | 47 | | | 150-199, 275-299 |
| 072 | 24 | | PK | 49-0 | 73-33-11 | D05306P | | 51 | | D04482J | | 48 | | | 050-099 |
| 072 | 24 | | PK | 59-0 | 73-33-11 | D05306P | | 51 | | D04482J | | 48 | | | 150-199, 275-299 |
| 073 | 24 | | PK | 49-0 | 73-33-11 | D05306P | | 52 | | D04482J | | 49 | | | 050-099 |
| 073 | 24 | | PK | 59-0 | 73-33-11 | D05306P | | 52 | | D04482J | | 49 | | | 150-199, 275-299 |
| 074 | 22 | | PA | 48-0 | 32-71-11 | D06186J | | 32 | | D08022J | | 23 | | | 150-199, 275-299 |
| 077 | 22 | | PA | 49-0 | 30-21-11 | D05306P | | 8 | | D04482J | | 8 | | | 050-099 |
| 077 | 22 | | PA | 59-0 | 30-21-11 | D05306P | | 8 | | D04482J | | 8 | | | 150-199, 275-299 |
| 103 | 24 | | PK | 49-0 | 78-36-11 | D05306P | | 29 | | D04482J | | 39 | | | 050-099 |
| 103 | 24 | | PK | 69-0 | 78-36-11 | D04482J | | 39 | | D05306P | | 29 | | | 150-156, 162-199 |
| 103 | 24 | | PK | 59-0 | 78-36-11 | D04482J | | 39 | | D05306P | | 29 | | | 157, 275-299 |
| 201B | 24 | | PW IA | 47-0 | 73-21-14 | D06186J | | 21 | | D05306P | | 49 | | | 050-099, 275-299 |
| 201B | 24 | | PW A | 47-0 | 73-21-14 | D06186J | | 21 | | D05306P | | 49 | | | 150-199 |
| 201R | 24 | | PW IA | 0-0 | 73-21-14 | D06186J | | 22 | | D05306P | | 50 | | | 050-099, 275-299 |
| 201R | 24 | | PW A | 0-0 | 73-21-14 | D06186J | | 22 | | D05306P | | 50 | | | 150-199 |
| 201Z | | | IA | 0-0 | 73-21-14 | D06186J | | 25 | | D05306P | | 46 | | | 050-099, 275-299 |
| 201Z | | | A | 0-0 | 73-21-14 | D06186J | | 25 | | D05306P | | 46 | | | 150-199 |
| 203R | 20 | | RJ C | 56-0 | 77-31-11 | D04482J | | 27 | | D08022J | | 1 | | | 150-154 |
| 203R | 20 | | RJ IC | 56-0 | 77-31-11 | D04482J | | 27 | | D08022J | | 1 | | | 275-276 |

WIRE LIST

D280T132

91-21-11
Section W0740
Page 7
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|----------|-------|---------|-------|------|------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0746 | 286T0746 | | | P61 TO L WING FS -L2A- FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 203W | 20 | RJ | C | 0-0 | 77-31-11 | | D04482J | 28 | | | D08022J | 2 | | | 150-154 |
| 203W | 20 | RJ | IC | 0-0 | 77-31-11 | | D04482J | 28 | | | D08022J | 2 | | | 275-276 |
| 203Z | | | C | 0-0 | 77-31-11 | | D04482J | 29 | | | D08022J | 3 | | | 150-154 |
| 203Z | | | IC | 0-0 | 77-31-11 | | D04482J | 29 | | | D08022J | 3 | | | 275-276 |
| 204B | 24 | PL | ID | 46-0 | 78-36-11 | | D08022J | 4 | | | D04482J | 30 | | | 050-099 |
| 204B | 24 | PL | D | 56-0 | 78-36-11 | | D04482J | 30 | | | D08022J | 4 | | | 150-199 |
| 204B | 24 | PL | ID | 56-0 | 78-36-11 | | D04482J | 30 | | | D08022J | 4 | | | 275-299 |
| 204R | 24 | PL | ID | 0-0 | 78-36-11 | | D08022J | 5 | | | D04482J | 31 | | | 050-099 |
| 204R | 24 | PL | D | 0-0 | 78-36-11 | | D04482J | 31 | | | D08022J | 5 | | | 150-199 |
| 204R | 24 | PL | ID | 0-0 | 78-36-11 | | D04482J | 31 | | | D08022J | 5 | | | 275-299 |
| 205B | 24 | PL | IE | 46-0 | 78-36-11 | | D08022J | 6 | | | D04482J | 32 | | | 050-099 |
| 205B | 24 | PL | E | 56-0 | 78-36-11 | | D04482J | 32 | | | D08022J | 6 | | | 150-199 |
| 205B | 24 | PL | IE | 56-0 | 78-36-11 | | D04482J | 32 | | | D08022J | 6 | | | 275-299 |
| 205R | 24 | PL | IE | 0-0 | 78-36-11 | | D08022J | 7 | | | D04482J | 33 | | | 050-099 |
| 205R | 24 | PL | E | 0-0 | 78-36-11 | | D04482J | 33 | | | D08022J | 7 | | | 150-199 |
| 205R | 24 | PL | IE | 0-0 | 78-36-11 | | D04482J | 33 | | | D08022J | 7 | | | 275-299 |
| 206B | 24 | PL | IF | 46-0 | 78-36-11 | | D08022J | 8 | | | D04482J | 34 | | | 050-099 |
| 206B | 24 | PL | F | 56-0 | 78-36-11 | | D04482J | 34 | | | D08022J | 8 | | | 150-199 |
| 206B | 24 | PL | IF | 56-0 | 78-36-11 | | D04482J | 34 | | | D08022J | 8 | | | 275-299 |
| 206R | 24 | PL | IF | 0-0 | 78-36-11 | | D08022J | 9 | | | D04482J | 35 | | | 050-099 |
| 206R | 24 | PL | F | 0-0 | 78-36-11 | | D04482J | 35 | | | D08022J | 9 | | | 150-199 |
| 206R | 24 | PL | IF | 0-0 | 78-36-11 | | D04482J | 35 | | | D08022J | 9 | | | 275-299 |
| 207B | 24 | PL | IG | 46-0 | 78-36-11 | | D08022J | 10 | | | D04482J | 36 | | | 050-099 |
| 207B | 24 | PL | G | 56-0 | 78-36-11 | | D04482J | 36 | | | D08022J | 10 | | | 150-199 |
| 207B | 24 | PL | IG | 56-0 | 78-36-11 | | D04482J | 36 | | | D08022J | 10 | | | 275-299 |
| 207R | 24 | PL | IG | 0-0 | 78-36-11 | | D08022J | 11 | | | D04482J | 37 | | | 050-099 |
| 207R | 24 | PL | G | 0-0 | 78-36-11 | | D04482J | 37 | | | D08022J | 11 | | | 150-199 |
| 207R | 24 | PL | IG | 0-0 | 78-36-11 | | D04482J | 37 | | | D08022J | 11 | | | 275-299 |
| 210B | 20 | PB | M | 87-0 | SPARE | | D04482J | 10 | | | D04732P | 22 | | | 150-199 |
| 210B | 20 | PB | IJ | 87-0 | SPARE | | D04482J | 10 | | | D04732P | 22 | | | 275-299 |
| 210R | 20 | PB | M | 0-0 | SPARE | | D04482J | 11 | | | D04732P | 23 | | | 150-199 |
| 210R | 20 | PB | IJ | 0-0 | SPARE | | D04482J | 11 | | | D04732P | 23 | | | 275-299 |
| 211B | 24 | PL | P | 59-0 | SPARE | | D04482J | 19 | | | D05306P | 35 | | | 150-199 |
| 211B | 24 | PL | IK | 59-0 | SPARE | | D04482J | 18 | | | D05306P | 35 | | | 275-299 |
| 211R | 24 | PL | P | 0-0 | SPARE | | D04482J | 20 | | | D05306P | 36 | | | 150-199 |
| 211R | 24 | PL | IK | 0-0 | SPARE | | D04482J | 19 | | | D05306P | 36 | | | 275-299 |
| 301B | 24 | PM | MA | 49-0 | 79-31-11 | | D05306P | 41 | | | D04482J | 2 | | | 050-099 |
| 301B | 24 | PM | V | 59-0 | 79-31-11 | | D04482J | 2 | | | D05306P | 41 | | | 150-199 |
| 301B | 24 | PM | MA | 59-0 | 79-31-11 | | D04482J | 2 | | | D05306P | 41 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0740

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0746 | 286T0746 | | | P61 TO L WING FS -L2A- FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | | |
| 301R | 24 | | PM | MA | 0-0 | 79-31-11 | D05306P | | 40 | | | | D04482J | | 4 | | | 050-099 |
| 301R | 24 | | PM | V | 0-0 | 79-31-11 | D04482J | | 4 | | | | D05306P | | 40 | | | 150-199 |
| 301R | 24 | | PM | MA | 0-0 | 79-31-11 | D04482J | | 4 | | | | D05306P | | 40 | | | 275-299 |
| 301Y | 24 | | PM | MA | 0-0 | 79-31-11 | D05306P | | 39 | | | | D04482J | | 3 | | | 050-099 |
| 301Y | 24 | | PM | V | 0-0 | 79-31-11 | D04482J | | 3 | | | | D05306P | | 39 | | | 150-199 |
| 301Y | 24 | | PM | MA | 0-0 | 79-31-11 | D04482J | | 3 | | | | D05306P | | 39 | | | 275-299 |
| 302B | 24 | | PX | MB | 49-0 | 73-31-11 | D05306P | | 31 | | | | D04482J | | 25 | | | 050-099 |
| 302B | 24 | | PX | MB | 59-0 | 73-31-11 | D04482J | | 25 | | | | D05306P | | 31 | | | 150-199 |
| 302B | 24 | | PX | MB | 59-0 | 73-31-11 | D05306P | | 31 | | | | D04482J | | 25 | | | 275-299 |
| 302R | 24 | | PX | MB | 0-0 | 73-31-11 | D05306P | | 33 | | | | D04482J | | 24 | | | 050-099, 275-299 |
| 302R | 24 | | PX | MB | 0-0 | 73-31-11 | D04482J | | 24 | | | | D05306P | | 33 | | | 150-199 |
| 302Y | 24 | | PX | MB | 0-0 | 73-31-11 | D05306P | | 34 | | | | D04482J | | 26 | | | 050-099, 275-299 |
| 302Y | 24 | | PX | MB | 0-0 | 73-31-11 | D04482J | | 26 | | | | D05306P | | 34 | | | 150-199 |
| 302Z | | | | MB | 0-0 | 73-31-11 | D05306P | | 13 | | | | D04482J | | 23 | | | 050-099, 275-299 |
| 302Z | | | | MB | 0-0 | 73-31-11 | D04482J | | 23 | | | | D05306P | | 13 | | | 150-199 |
| 505 | 20 | | UA | | 6-0 | 78-34-11 | D05306P | | | | | FA | GD00670 | | S.. | 2 | | 050-099, 150-156, 162-199, 275-299 |
| 505 | 20 | | UA | | 3-0 | 78-34-11 | D05306P | | | | | FA | GD00670 | | S.. | 2 | | 157 |
| 506 | 18 | | PQ | UF | 49-0 | 78-34-11 | D05306P | | 23 | DK | | | D04482J | | 54 | DK | | 050-099 |
| 506 | 18 | | PQ | UF | 69-0 | 78-34-11 | D05306P | | 23 | DK | | | D04482J | | 54 | DK | | 150-156, 162-199 |
| 506 | 18 | | PQ | UF | 59-0 | 78-34-11 | D05306P | | 23 | DK | | | D04482J | | 54 | DK | | 157, 275-299 |
| 506Z | | | | UF | 0-0 | 78-34-11 | D05306P | | | | | FA | D04482J | | =CC | D | | ALL |
| 507 | 18 | | PQ | UG | 49-0 | 78-34-11 | D05306P | | 24 | DK | | | D04482J | | 55 | DK | | 050-099 |
| 507 | 18 | | PQ | UG | 69-0 | 78-34-11 | D05306P | | 24 | DK | | | D04482J | | 55 | DK | | 150-156, 162-199 |
| 507 | 18 | | PQ | UG | 59-0 | 78-34-11 | D05306P | | 24 | DK | | | D04482J | | 55 | DK | | 157, 275-299 |
| 507Z | | | | UG | 0-0 | 78-34-11 | D05306P | | | | | FA | D04482J | | =CC | D | | ALL |
| FRA | | | | | 0-0 | 78-34-11 | D05306P | | 47 | | | | D05306P | | | | FA | ALL |
| W0748 | 286T0748 | | | P36 TO TAIL-L2A-FLT CONT | | | | | | | | | | | | | | |
| 001 | 24 | | PK | | 140-0 | 27-28-11 | D05436P | | 1 | | | | D05310P | | 1 | | | 050-099 |
| 001 | 24 | | PK | | 161-0 | 27-28-11 | D05436P | | 1 | | | | D05310P | | 1 | | | 150-199, 275-299 |
| 002 | 24 | | PK | | 140-0 | 27-28-11 | D05436P | | 2 | | | | D05310P | | 2 | | | 050-099 |
| 002 | 24 | | PK | | 161-0 | 27-28-11 | D05436P | | 2 | | | | D05310P | | 2 | | | 150-199, 275-299 |
| 003 | 24 | | PK | | 140-0 | 27-28-11 | D05436P | | 3 | | | | D05310P | | 3 | | | 050-099 |
| 003 | 24 | | PK | | 161-0 | 27-28-11 | D05436P | | 3 | | | | D05310P | | 3 | | | 150-199, 275-299 |
| 004 | 20 | | PA | | 140-0 | 27-23-11 | D05942P | | 2 | | | | D05310P | | 4 | | | 050-099 |
| 004 | 20 | | PA | | 161-0 | 27-23-11 | D05942P | | 2 | | | | D05310P | | 4 | | | 150-199, 275-299 |
| 005 | 22 | | PA | | 140-0 | 27-23-11 | D05942P | | 1 | | | | D05310P | | 5 | | | 050-099 |
| 005 | 22 | | PA | | 161-0 | 27-23-11 | D05942P | | 1 | | | | D05310P | | 5 | | | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0740
Page 9
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0748 | 286T0748 | | | P36 TO TAIL-L2A-FLT CONT (continued) | | | | | | | | | | | |
| 006 | 20 | | PA | 140-0 | 27-21-11 | D05436P | | 6 | | | D05310P | | 6 | | 050-099 |
| 006 | 20 | | PA | 161-0 | 27-21-11 | D05436P | | 6 | | | D05310P | | 6 | | 150-199, 275-299 |
| 007 | 20 | | PA | 140-0 | 27-23-11 | D05942P | | 3 | | | D05310P | | 7 | | 050-099 |
| 007 | 20 | | PA | 161-0 | 27-23-11 | D05942P | | 3 | | | D05310P | | 7 | | 150-199, 275-299 |
| 009 | 24 | | PK | 140-0 | 27-28-13 | D05436P | | 9 | | | D05310P | | 9 | | 050-099 |
| 009 | 24 | | PK | 161-0 | 27-28-13 | D05436P | | 9 | | | D05310P | | 9 | | 150-199, 275-299 |
| 010 | 22 | | PA | 140-0 | SPARE | D05436P | | 10 | | | D05310P | | 10 | | 050-099 |
| 011 | 18 | | PA | 161-0 | 32-71-11 | D05942P | | 4 | | | D05310P | | 8 | DL | 150-199, 275-299 |
| 012 | 18 | | PA | 160-0 | 32-71-11 | D05942P | | 5 | | | D05310P | | 10 | | 150-154, 162-165, 275-276 |
| 012 | 18 | | PA | 160-0 | 32-71-11 | D05942P | | 5 | | | D05310P | | 10 | DL | 155-157, 166-199, 277-299 |
| 013 | 24 | | PK | 161-0 | 27-28-11 | D05310P | | 13 | | | D05436P | | 4 | | 155-157, 166-199, 277-299 |
| 201B | 24 | | PL A | 140-0 | 27-28-13 | D05436P | | 12 | | | D05310P | | 12 | | 050-099 |
| 201B | 24 | | PL A | 161-0 | 27-28-13 | D05436P | | 12 | | | D05310P | | 12 | | 150-199, 275-299 |
| 201R | 24 | | PL A | 0-0 | 27-28-13 | D05436P | | 11 | | | D05310P | | 11 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0740
Page 10 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------|----|---------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0750 | 286T0750 | | | P36 TO TAIL-L2B-FLT CONT | | | | | | | | | | | | |
| 001 | 24 | | PK | | 131-0 | 27-38-11 | D05312P | | | | D05438P | | | | 050-099 | |
| 001 | 24 | | PK | | 154-0 | 27-38-11 | D05312P | | | | D05438P | | | | 150-199, 275-299 | |
| 002 | 24 | | PK | | 131-0 | 27-38-11 | D05312P | | | 2 | D05438P | | | | 050-099 | |
| 002 | 24 | | PK | | 154-0 | 27-38-11 | D05312P | | | 2 | D05438P | | | | 150-199, 275-299 | |
| 003 | 24 | | PK | | 131-0 | 27-38-11 | D05312P | | | 3 | D05438P | | | | 050-099 | |
| 003 | 24 | | PK | | 154-0 | 27-38-11 | D05312P | | | 3 | D05438P | | | | 150-199, 275-299 | |
| 004 | 20 | | PA | | 131-0 | 27-23-11 | D05312P | | | 4 | D05438P | | | | 050-099 | |
| 004 | 20 | | PA | | 154-0 | 27-23-11 | D05312P | | | 4 | D05438P | | | | 150-199, 275-299 | |
| 005 | 22 | | PA | | 131-0 | 27-23-11 | D05312P | | | 5 | D05438P | | | | 050-099 | |
| 005 | 22 | | PA | | 154-0 | 27-23-11 | D05312P | | | 5 | D05438P | | | | 150-199, 275-299 | |
| 006 | 24 | | PK | | 131-0 | 27-38-11 | D05312P | | | 6 | D05438P | | | | 050-099 | |
| 006 | 24 | | PK | | 154-0 | 27-38-11 | D05312P | | | 6 | D05438P | | | | 150-199, 275-299 | |
| 007 | 20 | | PA | | 131-0 | 27-23-11 | D05312P | | | 7 | D05438P | | | | 050-099 | |
| 007 | 20 | | PA | | 154-0 | 27-23-11 | D05312P | | | 7 | D05438P | | | | 150-199, 275-299 | |
| 008 | 24 | | PK | | 131-0 | 27-38-11 | D05312P | | | 8 | D05438P | | | | 050-099 | |
| 008 | 24 | | PK | | 154-0 | 27-38-11 | D05312P | | | 8 | D05438P | | | | 150-199, 275-299 | |
| 009 | 24 | | PK | | 131-0 | 27-38-11 | D05312P | | | 9 | D05438P | | | | 050-099 | |
| 009 | 24 | | PK | | 154-0 | 27-38-11 | D05312P | | | 9 | D05438P | | | | 150-199, 275-299 | |
| 010 | 22 | | PA | | 131-0 | 27-31-11 | D05312P | | | 10 | D05438P | | | | 050-099 | |
| 010 | 22 | | PA | | 154-0 | 27-31-11 | D05312P | | | 10 | D05438P | | | | 150-199, 275-299 | |
| 011 | 22 | | PA | | 131-0 | SPARE | D05312P | | | 11 | D05438P | | | | 050-099 | |
| 011 | 22 | | PA | | 154-0 | SPARE | D05312P | | | 11 | D05438P | | | | 150-154, 162-165, 275-276 | |
| 012 | 22 | | PA | | 131-0 | SPARE | D05312P | | | 12 | D05438P | | | | 050-099 | |
| 012 | 22 | | PA | | 154-0 | SPARE | D05312P | | | 12 | D05438P | | | | 150-154, 162-165, 275-276 | |
| 013 | 16 | | PA | | 131-0 | 33-45-11 | D05312P | | 13 | FL | D05438P | | 13 | FM | 050-099 | |
| 013 | 16 | | PA | | 154-0 | 33-45-11 | D05312P | | 13 | FL | D05438P | | 13 | FM | 150-199, 275-299 | |
| 014 | 16 | | PA | | 131-0 | 33-45-11 | D05312P | | 14 | FL | D05438P | | 14 | FM | 050-099 | |
| 014 | 16 | | PA | | 154-0 | 33-45-11 | D05312P | | 14 | FL | D05438P | | 14 | FM | 150-199, 275-299 | |
| 015 | 24 | | PK | | 154-0 | 27-38-11 | D05312P | | 15 | | D05438P | | 12 | | 155-157, 166-199, 277-299 | |
| 020 | 24 | | PK | | 154-0 | 27-38-11 | D05312P | | 11 | | D05438P | | 11 | | 155-157, 166-199, 277-299 | |
| W0751 | 286T0751 | | | IRS-L,SHELF TO SEL PNL | | | | | | | | | | | | |
| 001 | 20 | | PA | | 6-11 | 33-13-16 | TB0068H | | 1 | 2 | D00739 | | 1 | | ALL | |
| 002 | 20 | | PA | | 6-0 | 33-13-16 | GD00263 | | A.. | 2 | D00739 | | 2 | | ALL | |
| 003 | 20 | | PA | | 37-0 | 34-21-11 | D04699J | | 3 | | D00739 | | 3 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|---------|-------------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0751 | 286T0751 | | | IRS-L,SHELF TO SEL PNL (continued) | | | | | | | | | | | |
| 004 | 20 | PA | | | 37-0 | 34-21-11 | D04699J | | 4 | | | D00739 | 4 | | ALL |
| 005 | 20 | PA | | | 37-0 | 34-21-11 | D04699J | | 5 | | | D00739 | 5 | | ALL |
| 008 | 20 | PA | | | 6-0 | 34-21-11 | GD00263 | S.. | 2 | | | D00739 | 8 | | ALL |
| 010 | 22 | PA | | | 6-0 | 33-16-17 | TB0070Y | C036 | | BJ | | D00739 | 10 | | ALL |
| 012 | 24 | PK | | | 37-0 | 34-21-11 | D04699J | | 12 | | | D00739 | 12 | | ALL |
| 013 | 24 | PK | | | 37-0 | 34-21-11 | D04699J | | 13 | | | D00739 | 13 | | ALL |
| 014 | 22 | PA | | | 37-0 | 34-21-11 | D04699J | | 14 | | | D00739 | 14 | | ALL |
| 015 | 22 | PA | | | 37-0 | 34-21-11 | D04699J | | 15 | | | D00739 | 15 | | ALL |
| 016 | 22 | PA | | | 37-0 | 34-21-11 | D04699J | | 16 | | | D00739 | 16 | | ALL |
| 017 | 22 | PA | | | 37-0 | 34-21-11 | D04699J | | 17 | | | D00739 | 17 | | ALL |
| 018 | 22 | PA | | | 6-0 | 33-16-17 | TB0070Y | A036 | | BJ | | D00739 | 18 | | ALL |
| 019 | 22 | PA | | | 6-0 | 33-16-17 | TB0070Y | C036 | | BJ | | D00739 | 11 | | ALL |
| 020 | 24 | PK | | | 7-0 | 21-58-11 | D00739 | | 20 | | | TB0066Y | A022 | BJ | ALL |
| 021 | 24 | PK | | | 7-0 | 21-58-11 | D00739 | | 19 | | | TB0066Z | 23 | BJ | ALL |
| 028 | 22 | PA | | | 21-0 | 33-16-17 | D04699J | | 8 | | | TB0031F | A026 | 2 | ALL |
| 201 | 20 | UA | | | 1-6 | 34-21-11 | D00739 | REF | | FA | | GD00709 | S.. | E | ALL |
| 201B | 24 | PW | IA | | 37-0 | 34-21-11 | D04699J | | 20 | | | D00739 | 27 | | ALL |
| 201R | 24 | PW | IA | | 0-0 | 34-21-11 | D04699J | | 19 | | | D00739 | 26 | | ALL |
| 201Z | | | IA | | 0-0 | 34-21-11 | D04699J | | 21 | | | D00739 | REF | | FA |
| 202 | 20 | UA | | | 1-6 | 34-21-11 | D00739 | REF | | FB | | GD00709 | S.. | E | ALL |
| 202B | 24 | PW | IB | | 37-0 | 34-21-11 | D04699J | | 23 | | | D00739 | 25 | | ALL |
| 202R | 24 | PW | IB | | 0-0 | 34-21-11 | D04699J | | 24 | | | D00739 | 24 | | ALL |
| 202Z | | | IB | | 0-0 | 34-21-11 | D04699J | | 22 | | | D00739 | REF | | FB |
| W0752 | 286T0752 | | | P61 TO R WING RS -L2- FLT CONT | | | | | | | | | | | |
| 001 | 22 | PA | | | 78-2 | 27-18-11 | D04718P | | 1 | | | D04272J | 1 | | 050-099 |
| 001 | 22 | PA | | | 87-11 | 27-18-11 | D04718P | | 1 | | | D04272J | 1 | | 150-199, 275-299 |
| 002 | 22 | PA | | | 70-7 | 27-18-11 | D05330P | | 14 | | | D04272J | 2 | | 050-099 |
| 002 | 22 | PA | | | 80-4 | 27-18-11 | D05330P | | 14 | | | D04272J | 2 | | 150-156, 162-166, 275-276 |
| 002 | 22 | PA | | | 80-4 | SPARE | D05330P | | 14 | | | D04272J | 2 | | 157, 167-199, 277-299 |
| 003 | 22 | PA | | | 70-7 | 27-18-11 | D05330P | | 15 | | | D04272J | 3 | | 050-099 |
| 003 | 22 | PA | | | 80-4 | 27-18-11 | D05330P | | 15 | | | D04272J | 3 | | 150-156, 162-166, 275-276 |
| 003 | 22 | PA | | | 80-4 | SPARE | D05330P | | 15 | | | D04272J | 3 | | 157, 167-199, 277-299 |
| 004 | 20 | PA | | | 87-10 | 27-51-31 | D05894P | | 6 | | | D05414J | 1 | | 050-099 |
| 004 | 20 | PA | | | 97-7 | 27-51-31 | D05894P | | 6 | | | D05414J | 1 | | 150-199, 275-299 |
| 005 | 20 | PA | | | 6-0 | 27-51-31 | D05414J | | 2 | | | GD00794 | D.. 2 | | 050-099 |
| 005 | 20 | PA | | | 4-11 | 27-51-31 | D05414J | | 2 | | | GD00794 | D.. 2 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0752 | 286T0752 | | | P61 TO R WING RS -L2- FLT CONT (continued) | | | | | | | | | | | |
| 006 | 22 | | PA | | 78-2 | 27-18-11 | D04718P | | | | D04272J | | 4 | | 050-099 |
| 006 | 22 | | PA | | 87-11 | 27-18-11 | D04718P | | | | D04272J | | 4 | | 150-199, 275-299 |
| 007 | 22 | | PA | | 70-9 | 27-18-11 | D05330P | | | | SP02634 | | | 9 | 050-099 |
| 007 | 22 | | PA | | 80-5 | 27-18-11 | D05330P | | | | SP02634 | | | 9 | 150-154, 162-165, 275-276 |
| 008 | 22 | | PA | | 70-9 | 27-18-11 | D05330P | | | | SP02630 | | | 9 | 050-099 |
| 008 | 22 | | PA | | 80-5 | 27-18-11 | D05330P | | | | SP02630 | | | 9 | 150-154, 162-165, 275-276 |
| 009 | 20 | | PA | | 87-10 | 27-81-31 | D05894P | | | | D05414J | | | 4 | 050-099 |
| 009 | 20 | | PA | | 97-7 | 27-81-31 | D05894P | | | | D05414J | | | 4 | 150-199, 275-299 |
| 010 | 20 | | PA | | 6-0 | 27-81-31 | D05414J | | | | GD00794 | | S.. | 2 | 050-099 |
| 010 | 20 | | PA | | 4-11 | 27-81-31 | D05414J | | | | GD00794 | | S.. | 2 | 150-199, 275-299 |
| 011 | 20 | | PA | | 83-0 | 27-62-11 | D04272J | | | | D05662P | | | 4 | 050-099 |
| 011 | 20 | | PA | | 92-9 | 27-62-11 | D04272J | | | | D05662P | | | 4 | 150-199, 275-299 |
| 012 | 20 | | PA | | 6-0 | 27-81-31 | D05414J | | | | GD00794 | | D.. | 2 | 050-099 |
| 012 | 20 | | PA | | 4-11 | 27-81-31 | D05414J | | | | GD00794 | | D.. | 2 | 150-199, 275-299 |
| 013 | 20 | | PA | | 86-3 | 27-51-51 | D05662P | | | | D05414J | | | 6 | 050-099 |
| 013 | 20 | | PA | | 96-1 | 27-51-51 | D05662P | | | | D05414J | | | 6 | 150-199, 275-299 |
| 014 | 22 | | PA | | 83-0 | 27-58-11 | D05662P | | | | D04272J | | | 8 | 050-099 |
| 014 | 22 | | PA | | 92-9 | 27-58-11 | D05662P | | | | D04272J | | | 8 | 150-155, 162-165, 275-276 |
| 015 | 22 | | PA | | 83-0 | 27-58-11 | D05662P | | | | D04272J | | | 9 | 050-099 |
| 015 | 22 | | PA | | 92-9 | 27-58-11 | D05662P | | | | D04272J | | | 9 | 150-155, 162-165, 275-276 |
| 016 | 22 | | PA | | 83-0 | 27-58-11 | D05662P | | | | D04272J | | | 10 | 050-099 |
| 016 | 22 | | PA | | 92-9 | 27-58-11 | D05662P | | | | D04272J | | | 10 | 150-199, 275-299 |
| 017 | 20 | | PA | | 86-3 | 27-51-51 | D05662P | | | | D05414J | | | 7 | 050-099 |
| 017 | 20 | | PA | | 96-1 | 27-51-51 | D05662P | | | | D05414J | | | 7 | 150-199, 275-299 |
| 018 | 20 | | PA | | 6-0 | 27-51-51 | D05414J | | | | GD00794 | | D.. | 2 | 050-099 |
| 018 | 20 | | PA | | 4-11 | 27-51-51 | D05414J | | | | GD00794 | | D.. | 2 | 150-199, 275-299 |
| 019 | 20 | | PA | | 83-0 | 27-62-11 | D05662P | | | | D04272J | | | 11 | 050-099 |
| 019 | 20 | | PA | | 92-9 | 27-62-11 | D05662P | | | | D04272J | | | 11 | 150-199, 275-299 |
| 020 | 20 | | PA | | 6-0 | 27-51-51 | D05414J | | | | GD00794 | | S.. | 2 | 050-099 |
| 020 | 20 | | PA | | 4-11 | 27-51-51 | D05414J | | | | GD00794 | | S.. | 2 | 150-199, 275-299 |
| 021 | 24 | | PK | | 15-4 | 22-41-11 | D05330P | | | | D05662P | | | 1 | ALL |
| 022 | 12 | | PA | | 32-6 | 28-22-12 | D04718P | | | | D05894P | | | 20 | ALL |
| 023 | 12 | | PA | | 32-6 | 28-22-12 | D04718P | | | | D05894P | | | 22 | ALL |
| 024 | 12 | | PA | | 32-6 | 28-22-12 | D04718P | | | | D05894P | | | 24 | ALL |
| 025 | 20 | | PA | | 33-0 | SPARE | D04718P | | CAP | Y | D05894P | | CAP | Y | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 3

Mar 09/2006



| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0752 | 286T0752 | | | P61 TO R WING RS -L2- FLT CONT (continued) | | | | | | | | | | | |
| 025 | 20 | | PA | | 32-6 | SPARE | D04718P | 2 | DL | | D05894P | 2 | DL | | 275 |
| 025 | 18 | | PA | | 32-6 | 25-31-31 | D04718P | 11 | DL | | D05894P | 2 | DL | | 277-299 |
| 027 | 24 | | PK | | 32-6 | 27-51-31 | D05894P | 1 | | | D04718P | 8 | | | ALL |
| 029 | 24 | | PK | | 32-6 | 27-81-31 | D05894P | 3 | | | D04718P | 10 | | | ALL |
| 030 | 22 | | PA | | 30-11 | SPARE | D04718P | 9 | | | D05662P | 6 | | | 150-199 |
| 031 | 20 | | PA | | 18-0 | SPARE | D05894P | | CAP | Y | D05330P | 20 | | | ALL |
| 032 | 22 | | PA | | 70-7 | 28-42-11 | D04272J | 12 | | | D05330P | 21 | | | 050-099 |
| 032 | 22 | | PA | | 80-4 | 28-42-11 | D04272J | 12 | | | D05330P | 21 | | | 150-199, 275-299 |
| 033 | 22 | | PA | | 70-7 | 28-42-12 | D04272J | 13 | | | D05330P | 22 | | | 050-099 |
| 033 | 22 | | PA | | 80-4 | 28-42-12 | D04272J | 13 | | | D05330P | 22 | | | 150-199, 275-299 |
| 034 | 22 | | PA | | 80-4 | SPARE | D04272J | 14 | | | D05330P | 23 | | | 150-199, 275-299 |
| 036 | 22 | | PA | | 47-3 | SPARE | D08024J | 30 | | | D04626J | 6 | | | 050-099 |
| 036 | 22 | | PA | | 58-2 | SPARE | D08024J | 30 | | | D04626J | 6 | | | 150-199, 275-299 |
| 037 | 22 | | PA | | 47-3 | SPARE | D08024J | 31 | | | D04626J | 7 | | | 050-099 |
| 037 | 22 | | PA | | 58-2 | SPARE | D08024J | 31 | | | D04626J | 7 | | | 150-199, 275-299 |
| 038 | 22 | | PA | | 30-11 | 30-32-11 | D05662P | 2 | | | D04718P | 12 | | | ALL |
| 040 | 20 | | PA | | 4-6 | 27-18-11 | D04272J | 21 | | | GD04168 | A.. | 2 | | 050-099 |
| 040 | 20 | | PA | | 4-2 | 27-18-11 | D04272J | 21 | | | GD04168 | A.. | 2 | | 150-199, 275-299 |
| 042 | 20 | | PA | | 4-6 | 27-18-11 | D04272J | 23 | | | GD04168 | A.. | 2 | | 050-099 |
| 042 | 20 | | PA | | 4-2 | 27-18-11 | D04272J | 23 | | | GD04168 | A.. | 2 | | 150-199, 275-299 |
| 043 | 18 | | PA | | 18-6 | 33-44-21 | D05330P | 19 | DK | | D04718P | 16 | DL | | 050-099, 150-156, 162-166, 275-276 |
| 043 | 18 | | PA | | 18-6 | 33-44-21 | D05330P | 19 | DK | | D04718P | 16 | DK | | 157, 167-199, 277-299 |
| 044 | 20 | | PA | | 4-6 | 27-58-11 | D04272J | 24 | | | GD04168 | A.. | 2 | | 050-099 |
| 044 | 20 | | PA | | 4-2 | 27-58-11 | D04272J | 24 | | | GD04168 | A.. | 2 | | 150-155, 162-165, 275-276 |
| 047 | 20 | | PA | | 32-6 | 25-31-21 | D05894P | 8 | | | D04718P | 22 | | | 050-099, 150-199 |
| 047 | 18 | | PA | | 32-6 | 25-31-21 | D05894P | 18 | FL | | D04718P | 18 | FL | | 275-276 |
| 047 | 18 | | PA | | 32-6 | 25-31-21 | D05894P | 18 | | | D04718P | 18 | DL | | 277-278 |
| 047 | 18 | | PA | | 32-6 | 25-31-21 | D05894P | 18 | | | D04718P | 18 | DK | | 280-299 |
| 048 | 22 | | PA | | 15-4 | 78-36-11 | D05330P | 2 | | | D05662P | 7 | | | ALL |
| 050 | 22 | | PQ | N | 15-4 | 29-11-22 | D05330P | 3 | | | D05662P | 5 | | | ALL |
| 050Z | | | | N | 0-0 | 29-11-22 | D05330P | DED | | | D05662P | DED | | | ALL |
| 051 | 22 | | PA | | 28-2 | 28-41-13 | D08024J | 35 | | | D04718P | 5 | | | ALL |
| 052 | 24 | | PK | | 33-1 | 29-11-22 | D05662P | 13 | | | D08024J | 38 | | | ALL |
| 053 | 24 | | PK | | 33-1 | 29-11-22 | D05662P | 14 | | | D08024J | 39 | | | ALL |
| 070 | 22 | | PA | | 32-6 | 28-31-12 | D04718P | 20 | | | D05894P | 4 | | | 050-099, 155-199, 276-299 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0752 | 286T0752 | | | P61 TO R WING RS -L2- FLT CONT (continued) | | | | | | | | | | | | | |
| 071 | 20 | | PA | 32-6 | 28-31-12 | D04718P | | 17 | | | | | D05894P | 9 | | | 050-099, 155-199, 276-299 |
| 072 | 22 | | PA | 15-4 | SPARE | D05662P | | 21 | | | | | D05330P | 4 | | | 150-199, 275-299 |
| 073 | 22 | | PA | 15-4 | SPARE | D05662P | | 22 | | | | | D05330P | 5 | | | 150-199, 275-299 |
| 075 | 22 | | PA | 73-10 | SPARE | D05414J | | 10 | | | | | D05330P | 24 | | | 050-099 |
| 076 | 20 | | PA | 70-1 | SPARE | D05414J | | 11 | | | | | D08024J | 33 | | | 050-099 |
| 076 | 20 | | PA | 79-10 | SPARE | D05414J | | 11 | | | | | D08024J | 33 | | | 150-199, 275-299 |
| 077 | 22 | | PA | 71-0 | SPARE | D05414J | | | CAP | Y | | | D08024J | 32 | | | 050-099 |
| 077 | 22 | | PA | 80-0 | SPARE | D05414J | | | CAP | Y | | | D08024J | 32 | | | 150-199, 275-299 |
| 078 | 22 | | PA | 18-6 | SPARE | D05330P | | 13 | | | | | D04718P | 13 | | | 150-154, 275-276 |
| 079 | 22 | | PA | 35-0 | SPARE | D05662P | | | CAP | Y | | | D04718P | | CAP | Y | 150-154, 275 |
| 080 | 22 | | PA | 30-11 | SPARE | D05662P | | 19 | | | | | D04718P | 11 | | | 150-199, 275-276 |
| 080 | 22 | | PA | 35-0 | SPARE | D05662P | | 19 | | | | | D04718P | | CAP | Y | 280-299 |
| 081 | 22 | | PA | 9-3 | SPARE | D05662P | | 20 | | | | | D05894P | 4 | | | 150-154, 275 |
| 086 | 24 | | PK | 33-0 | SPARE | D04718P | | | CAP | Y | | | D05894P | 19 | | | ALL |
| 090 | 20 | | PA | 32-6 | 28-31-12 | D04718P | | 3 | | | | | D05894P | 10 | | | 050-099, 155-199, 276-299 |
| 091 | 22 | | PA | 32-6 | 28-42-12 | D04718P | | 2 | | | | | D05894P | 13 | | | 050-099, 155-199, 276-299 |
| 093 | 22 | | PA | 32-6 | 28-42-13 | D04718P | | 21 | | | | | D05894P | 11 | | | 050-099, 155-199, 276-299 |
| 094 | 20 | | PA | 32-6 | 28-31-12 | D04718P | | 13 | | | | | D05894P | 17 | | | 050-099, 155-199, 277-299 |
| 097 | 24 | | PK | 70-1 | 27-81-31 | D08024J | | 40 | | | | | D05414J | 14 | | | 050-099 |
| 097 | 24 | | PK | 79-10 | 27-81-31 | D08024J | | 40 | | | | | D05414J | 14 | | | 150-199, 275-299 |
| 098 | 24 | | PK | 70-1 | 27-81-31 | D08024J | | 41 | | | | | D05414J | 13 | | | 050-099 |
| 098 | 24 | | PK | 79-10 | 27-81-31 | D08024J | | 41 | | | | | D05414J | 13 | | | 150-199, 275-299 |
| 099 | 20 | | PA | 6-0 | 27-81-31 | D05414J | | 12 | | | | | GD00794 | | D.. | 2 | 050-099 |
| 099 | 20 | | PA | 4-11 | 27-81-31 | D05414J | | 12 | | | | | GD00794 | | D.. | 2 | 150-199, 275-299 |
| 122 | 22 | | PA | 67-0 | 27-89-11 | D04626J | | 12 | | | | | D05330P | 13 | | | 050-099, 162-199 |
| 122 | 22 | | PA | 67-0 | 27-89-11 | D04626J | | 12 | | | | | D05330P | 24 | | | 150-157, 275-278 |
| 122 | 22 | | PA | 62-0 | 27-89-11 | D04626J | | 12 | | | | | D05330P | 24 | | | 280-299 |
| 123 | 22 | | PA | 76-0 | 27-89-11 | D04626J | | 11 | | | | | D05894P | 12 | | | 050-099, 150-157, 275-299 |
| 123 | 22 | | PA | 76-0 | 27-89-11 | D04626J | | 11 | | | | | D05894P | 2 | | | 162-199 |
| 201B | 22 | | PB | A | 66-9 | 27-51-41 | D08024J | | 1 | | | | D04416J | 1 | | | 050-099 |
| 201B | 22 | | PB | A | 76-5 | 27-51-41 | D08024J | | 1 | | | | D04416J | 1 | | | 150-199, 275-299 |
| 201R | 22 | | PB | A | 0-0 | 27-51-41 | D08024J | | 2 | | | | D04416J | 2 | | | ALL |
| 204B | 22 | | PB | G | 47-3 | 27-81-31 | D08024J | | 19 | | | | D04626J | 1 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|---|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0752 | 286T0752 | | | P61 TO R WING RS -L2- FLT CONT (continued) | | | | | | | | | | | | | | |
| 204B | 22 | | PB | G | 58-2 | 27-81-31 | D08024J | | 19 | | | | | D04626J | 1 | | | 150-199, 275-299 |
| 204R | 22 | | PB | G | 0-0 | 27-81-31 | D08024J | | 20 | | | | | D04626J | 2 | | | ALL |
| 205B | 22 | | PB | I | 20-8 | 27-51-41 | D08024J | | 24 | | | | | D05330P | 7 | | | ALL |
| 205R | 22 | | PB | I | 0-0 | 27-51-41 | D08024J | | 25 | | | | | D05330P | 8 | | | ALL |
| 207B | 24 | | PL | M | 28-2 | 28-41-13 | D08024J | | 37 | | | | | D04718P | 6 | | | ALL |
| 207R | 24 | | PL | M | 0-0 | 28-41-13 | D08024J | | 36 | | | | | D04718P | 7 | | | ALL |
| 301B | 24 | | PM | H | 47-3 | 27-81-31 | D08024J | | 21 | | | | | D04626J | 3 | | | 050-099 |
| 301B | 24 | | PM | H | 58-2 | 27-81-31 | D08024J | | 21 | | | | | D04626J | 3 | | | 150-199, 275-299 |
| 301R | 24 | | PM | H | 0-0 | 27-81-31 | D08024J | | 22 | | | | | D04626J | 4 | | | ALL |
| 301Y | 24 | | PM | H | 0-0 | 27-81-31 | D08024J | | 23 | | | | | D04626J | 5 | | | ALL |
| 303B | 20 | | PC | AE | 92-9 | 27-58-11 | D04272J | | 8 | | | | | D05662P | 10 | | | 156-157, 166-199, 277-299 |
| 303R | 20 | | PC | AE | 0-0 | 27-58-11 | D04272J | | 9 | | | | | D05662P | 11 | | | 156-157, 166-199, 277-299 |
| 303Y | 20 | | PC | AE | 0-0 | 27-58-11 | D04272J | | 24 | | | | | D05662P | 23 | | | 156-157, 166-199, 277-299 |
| 401B | 22 | | PD | B | 66-9 | 27-51-41 | D08024J | | 3 | | | | | D04416J | 3 | | | 050-099 |
| 401B | 22 | | PD | B | 76-5 | 27-51-41 | D08024J | | 3 | | | | | D04416J | 3 | | | 150-199, 275-299 |
| 401G | 22 | | PD | B | 0-0 | 27-51-41 | D08024J | | 6 | | | | | D04416J | 6 | | | ALL |
| 401R | 22 | | PD | B | 0-0 | 27-51-41 | D08024J | | 4 | | | | | D04416J | 4 | | | ALL |
| 401Y | 22 | | PD | B | 0-0 | 27-51-41 | D08024J | | 5 | | | | | D04416J | 5 | | | ALL |
| 404B | 24 | | PN | J | 20-8 | 27-51-41 | D08024J | | 26 | | | | | D05330P | 9 | | | ALL |
| 404G | 24 | | PN | J | 0-0 | 27-51-41 | D08024J | | 29 | | | | | D05330P | 12 | | | ALL |
| 404R | 24 | | PN | J | 0-0 | 27-51-41 | D08024J | | 27 | | | | | D05330P | 10 | | | ALL |
| 404Y | 24 | | PN | J | 0-0 | 27-51-41 | D08024J | | 28 | | | | | D05330P | 11 | | | ALL |
| 500 | 20 | | UA | | 14-0 | 78-34-11 | D05894P | | | | | | FB | GD00670 | S.. | 2 | | ALL |
| 501 | 20 | | PQ | C | 24-0 | 78-34-11 | D04284P | | 25 | | | | | D05894P | 21 | | | ALL |
| 501Z | | | | C | 0-0 | 78-34-11 | D04284P | | | | | | FA | D05894P | | | FB | ALL |
| 502 | 20 | | PQ | D | 20-0 | 78-34-11 | D04284P | | 24 | | | | | D05894P | 5 | | | ALL |
| 502Z | | | | D | 0-0 | 78-34-11 | D04284P | | | | | | FA | D05894P | | | FB | ALL |
| 503 | 20 | | PA | | 14-0 | 78-34-11 | D04284P | | | | | | FA | GD00754 | S.. | 2 | | ALL |
| 504 | 20 | | PQ | E | 30-11 | 78-34-11 | D05662P | | 17 | | | | | D04718P | 24 | | | ALL |
| 504Z | | | | E | 0-0 | 78-34-11 | D05662P | | | | | | FC | D04718P | | | FD | ALL |
| 505 | 20 | | PQ | F | 30-11 | 78-34-11 | D05662P | | 18 | | | | | D04718P | 28 | | | ALL |
| 505Z | | | | F | 0-0 | 78-34-11 | D05662P | | | | | | FC | D04718P | | | FD | ALL |
| A-A | | | | | 0-0 | 27-18-11 | SP02630 | | 9 | | | | | M01148 | B | | | 050-099, 150-154, 162-165, 275-276 |
| A-B | | | | | 0-0 | 27-18-11 | SP02634 | | 9 | | | | | M01149 | B | | | 050-099, 150-154, 162-165, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|---------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0752 | 286T0752 | | | P61 TO R WING RS -L2- FLT CONT (continued) | | | | | | | | | | | |
| FRA | | | | | 0-0 | 78-34-11 | D04284P | | | | FA | D04284P | 22 | | ALL |
| FRB | | | | | 0-0 | 78-34-11 | D05894P | | | | FB | D05894P | 15 | | ALL |
| FRC | | | | | 0-0 | 78-34-11 | D05662P | | | | FC | D05662P | 16 | | ALL |
| FRD | | | | | 0-0 | 78-34-11 | D04718P | | | | FD | D04718P | 26 | | ALL |
| W0754 | 286T0754 | | | E1 TO R WING BODY-L2-FLT CONT | | | | | | | | | | | |
| 201B | 24 | PL | A | | 52-0 | 27-88-22 | D05434J | | 1 | | | D04628J | 1 | | 050-099 |
| 201B | 24 | PL | A | | 61-3 | 27-88-22 | D05434J | | 1 | | | D04628J | 1 | | 150-199, 275-299 |
| 201R | 24 | PL | A | | 0-0 | 27-88-22 | D05434J | | 2 | | | D04628J | 2 | | ALL |
| 202B | 22 | PB | B | | 52-0 | SPARE | D05434J | | 23 | | | D04628J | 23 | | 050-099 |
| 202B | 22 | PB | B | | 61-3 | SPARE | D05434J | | 23 | | | D04628J | 23 | | 150-199, 275-299 |
| 202R | 22 | PB | B | | 0-0 | SPARE | D05434J | | 24 | | | D04628J | 24 | | ALL |
| 203B | 24 | PL | C | | 52-0 | 27-88-22 | D05434J | | 5 | | | D04628J | 5 | | 050-099 |
| 203B | 24 | PL | C | | 61-3 | 27-88-22 | D05434J | | 5 | | | D04628J | 5 | | 150-199, 275-299 |
| 203R | 24 | PL | C | | 0-0 | 27-88-22 | D05434J | | 6 | | | D04628J | 6 | | ALL |
| 204B | 24 | PL | D | | 52-0 | 27-88-22 | D05434J | | 7 | | | D04628J | 7 | | 050-099 |
| 204B | 24 | PL | D | | 61-3 | 27-88-22 | D05434J | | 7 | | | D04628J | 7 | | 150-199, 275-299 |
| 204R | 24 | PL | D | | 0-0 | 27-88-22 | D05434J | | 8 | | | D04628J | 8 | | ALL |
| 206B | 24 | PL | F | | 52-0 | 27-88-22 | D05434J | | 11 | | | D04628J | 11 | | 050-099 |
| 206B | 24 | PL | F | | 61-3 | 27-88-22 | D05434J | | 11 | | | D04628J | 11 | | 150-199, 275-299 |
| 206R | 24 | PL | F | | 0-0 | 27-88-22 | D05434J | | 12 | | | D04628J | 12 | | ALL |
| 207B | 24 | PL | G | | 52-0 | 27-88-22 | D05434J | | 13 | | | D04628J | 13 | | 050-099 |
| 207B | 24 | PL | G | | 61-3 | 27-88-22 | D05434J | | 13 | | | D04628J | 13 | | 150-199, 275-299 |
| 207R | 24 | PL | G | | 0-0 | 27-88-22 | D05434J | | 14 | | | D04628J | 14 | | ALL |
| 208B | 24 | PL | H | | 52-0 | 27-88-22 | D05434J | | 15 | | | D04628J | 15 | | 050-099 |
| 208B | 24 | PL | H | | 61-3 | 27-88-22 | D05434J | | 15 | | | D04628J | 15 | | 150-199, 275-299 |
| 208R | 24 | PL | H | | 0-0 | 27-88-22 | D05434J | | 16 | | | D04628J | 16 | | ALL |
| 209B | 24 | PL | J | | 52-0 | 27-88-22 | D05434J | | 17 | | | D04628J | 17 | | 050-099 |
| 209B | 24 | PL | J | | 61-3 | 27-88-22 | D05434J | | 17 | | | D04628J | 17 | | 150-199, 275-299 |
| 209R | 24 | PL | J | | 0-0 | 27-88-22 | D05434J | | 18 | | | D04628J | 18 | | ALL |
| 211B | 24 | PL | L | | 52-0 | 27-88-22 | D05434J | | 21 | | | D04628J | 21 | | 050-099 |
| 211B | 24 | PL | L | | 61-3 | 27-88-22 | D05434J | | 21 | | | D04628J | 21 | | 150-199, 275-299 |
| 211R | 24 | PL | L | | 0-0 | 27-88-22 | D05434J | | 22 | | | D04628J | 22 | | ALL |
| 212B | 24 | PL | N | | 52-0 | 27-88-22 | D05434J | | 3 | | | D04628J | 3 | | 050-099 |
| 212B | 24 | PL | N | | 61-3 | 27-88-22 | D05434J | | 3 | | | D04628J | 3 | | 150-199, 275-299 |
| 212R | 24 | PL | N | | 0-0 | 27-88-22 | D05434J | | 4 | | | D04628J | 4 | | ALL |
| 214B | 24 | PL | E | | 52-0 | 27-88-22 | D05434J | | 9 | | | D04628J | 9 | | 050-099 |
| 214B | 24 | PL | E | | 61-3 | 27-88-22 | D05434J | | 9 | | | D04628J | 9 | | 150-199, 275-299 |
| 214R | 24 | PL | E | | 0-0 | 27-88-22 | D05434J | | 10 | | | D04628J | 10 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0754 | 286T0754 | | | E1 TO R WING BODY-L2-FLT CONT (continued) | | | | | | | | | | | | | |
| 216B | 24 | PL | K | 52-0 | 27-88-22 | D05434J | | 25 | | | | | D04628J | 19 | | | 050-099 |
| 216B | 24 | PL | K | 61-3 | 27-88-22 | D05434J | | 25 | | | | | D04628J | 19 | | | 150-199, 275-299 |
| 216R | 24 | PL | K | 0-0 | 27-88-22 | D05434J | | 26 | | | | | D04628J | 20 | | | ALL |
| 217B | 24 | PL | M | 52-0 | 27-88-22 | D05434J | | 19 | | | | | D04628J | 25 | | | 050-099 |
| 217B | 24 | PL | M | 61-3 | 27-88-22 | D05434J | | 19 | | | | | D04628J | 25 | | | 150-199, 275-299 |
| 217R | 24 | PL | M | 0-0 | 27-88-22 | D05434J | | 20 | | | | | D04628J | 26 | | | ALL |
| 801 | 22 | PA | | 52-0 | SPARE | D04628J | | 27 | | | | | D05434J | 27 | | | 050-099 |
| 801 | 22 | PA | | 61-3 | SPARE | D04628J | | 27 | | | | | D05434J | 27 | | | 150-199, 275-299 |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR | | | | | | | | | | | | | |
| 004 | 22 | PA | | 37-1 | 78-36-11 | D05300P | | 42 | | | | | D04710P | 3 | | | 050-099 |
| 004 | 22 | PA | | 37-1 | 78-36-11 | D04710P | | 3 | | | | | D05300P | 42 | | | 150-199, 275-299 |
| 006 | 20 | UA | | 2-0 | 73-21-20 | D04710P | | | | | | FG | GD05398 | S.. | E | | 150-199 |
| 010 | 20 | UA | | 2-0 | 73-21-20 | D04710P | | | | | | FH | GD05398 | S.. | E | | 150-199 |
| 011 | 22 | PA | | 48-5 | 78-36-11 | D05300P | | 44 | | | | | D11830 | 8 | | | 050-099 |
| 011 | 22 | PA | | 48-5 | 78-36-11 | D11830 | | 8 | | | | | D05300P | 44 | | | 150-199, 275-299 |
| 012 | 16 | PQ | CA | 67-8 | 73-21-20 | D04528J | | 13 | FM | | | | D04710P | 18 | FL | | 050-099 |
| 012 | 16 | PQ | CA | 77-6 | 73-21-20 | D04710P | | 18 | FL | | | | D04528J | 13 | FM | | 150-199 |
| 012 | 20 | PQ | AG | 77-6 | 73-21-20 | D04710P | | 18 | | | | | D04528J | 13 | | | 275-276 |
| 012 | 16 | PQ | AL | 77-6 | 73-21-20 | D04710P | | 18 | FL | | | | D04528J | 13 | FM | | 277-278 |
| 012 | 16 | PQ | AG | 77-6 | 73-21-20 | D04710P | | 18 | FL | | | | D04528J | 13 | FM | | 280-299 |
| 012Z | | | CA | 0-0 | 73-21-20 | D04528J | | =CC | D | | | | GD05398 | S.. | E | | 050-099 |
| 012Z | | | CA | 0-0 | 73-21-20 | D04710P | | | | | | FG | D04528J | =CC | D | | 150-199 |
| 012Z | | | AG | 0-0 | 73-21-20 | GD05398 | | S.. | E | | | | D04528J | =CC | L | | 275-276 |
| 012Z | | | AL | 0-0 | 73-21-20 | GD05398 | | S.. | E | | | | D04528J | =CC | D | | 277-278 |
| 012Z | | | AG | 0-0 | 73-21-20 | GD05398 | | S.. | E | | | | D04528J | =CC | D | | 280-299 |
| 015 | 24 | PK | | 13-2 | 27-88-11 | D05626J | | 30 | | | | | D05368J | 6 | | | ALL |
| 016 | 24 | PK | | 13-2 | 27-88-11 | D05626J | | 31 | | | | | D05368J | 7 | | | ALL |
| 017 | 24 | PK | | 13-2 | 27-88-11 | D05626J | | 32 | | | | | D05368J | 8 | | | ALL |
| 018 | 24 | PK | | 13-2 | 27-88-11 | D05626J | | 33 | | | | | D05368J | 9 | | | ALL |
| 019 | 24 | PK | | 13-2 | 27-88-11 | D05626J | | 34 | | | | | D05368J | 10 | | | ALL |
| 020 | 24 | PK | | 13-2 | 27-88-11 | D05626J | | 35 | | | | | D05368J | 11 | | | ALL |
| 021 | 22 | PA | | 42-3 | 32-45-11 | D05832P | | 25 | | | | | D05664P | 19 | | | 050-099, 275-299 |
| 021 | 22 | PA | | 42-3 | 32-45-11 | D05664P | | 19 | | | | | D05832P | 25 | | | 150-199 |
| 022 | 24 | PV | AI | 48-10 | 73-21-11 | D05832P | | 33 | | | | | D04528J | 5 | | | 050-099 |
| 022 | 24 | PV | AI | 59-2 | 73-21-11 | D04528J | | 5 | | | | | D05832P | 33 | | | 150-199 |
| 022 | 24 | PV | AV | 59-2 | 73-21-11 | D05832P | | 33 | | | | | D04528J | 5 | | | 275-299 |
| 022Z | | | AI | 0-0 | 73-21-11 | D05832P | | | | | | FE | D04528J | =CC | D | | 050-099 |
| 022Z | | | AI | 0-0 | 73-21-11 | D04528J | | =CC | D | | | | D05832P | | | FE | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|---------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 022Z | | | | AV | 0-0 | 73-21-11 | D05832P | | | | FB | D04528J | =CC | L | 275-276 |
| 022Z | | | | AV | 0-0 | 73-21-11 | D05832P | | | | FE | D04528J | =CC | D | 277-299 |
| 023 | 24 | PV | | AH | 48-10 | 73-21-11 | D05832P | 34 | | | | D04528J | 4 | | 050-099 |
| 023 | 24 | PV | | AH | 59-2 | 73-21-11 | D04528J | 4 | | | | D05832P | 34 | | 150-199 |
| 023 | 24 | PV | | AW | 59-2 | 73-21-11 | D05832P | 34 | | | | D04528J | 4 | | 275-299 |
| 023Z | | | | AH | 0-0 | 73-21-11 | D05832P | | | | FE | D04528J | =CC | D | 050-099 |
| 023Z | | | | AH | 0-0 | 73-21-11 | D04528J | =CC | D | | | D05832P | | FE | 150-199 |
| 023Z | | | | AW | 0-0 | 73-21-11 | D05832P | | | | FB | D04528J | =CC | L | 275-276 |
| 023Z | | | | AW | 0-0 | 73-21-11 | D05832P | | | | FE | D04528J | =CC | D | 277-299 |
| 027 | 16 | PQ | | YD | 67-8 | SPARE | D04528J | CAP | Y | | | D04710P | 26 | FM | 050-099 |
| 027 | 16 | PQ | | BE | 77-6 | SPARE | D04710P | 26 | FL | | | D04528J | CAP | Y | 150-199 |
| 027 | 16 | PQ | | BB | 77-6 | SPARE | D04710P | 26 | FL | | | D04528J | CAP | Y | 275-276 |
| 027Z | | | | YD | 0-0 | SPARE | D04528J | DED | | | | D04710P | 14 | | 050-099 |
| 027Z | | | | BE | 0-0 | SPARE | D04710P | 14 | | | | D04528J | =CC | M | 150-154 |
| 027Z | | | | BE | 0-0 | SPARE | D04710P | 14 | | | | D04528J | DED | | 155-199 |
| 027Z | | | | BB | 0-0 | SPARE | D04710P | 14 | | | | D04528J | =CC | L | 275-276 |
| 030 | 24 | PK | | | 20-1 | 27-11-11 | D04714P | 21 | | | | D01830 | 12 | | ALL |
| 031 | 22 | PA | | | 31-2 | 32-45-11 | D04714P | 17 | | | | D05664P | 2 | | ALL |
| 032 | 20 | PA | | | 8-9 | 27-11-11 | GD02464 | D.. | 2 | | | D01830 | 8 | | ALL |
| 037 | 24 | PK | | | 30-0 | 78-34-11 | D04710P | 29 | | | | D05368J | 28 | | ALL |
| 039 | 24 | PK | | | 14-1 | 27-88-11 | D08034J | 19 | | | | D05368J | 30 | | ALL |
| 040 | 24 | PK | | | 14-1 | SPARE | D08034J | 20 | | | | D05368J | CAP | Y | 150-199, 275-299 |
| 041 | 24 | PK | | | 14-1 | SPARE | D08034J | 21 | | | | D05368J | 32 | | 150-199, 275-299 |
| 042 | 24 | PK | | | 14-1 | SPARE | D08034J | 22 | | | | D05368J | 33 | | 150-199, 275-299 |
| 043 | 24 | PK | | | 14-1 | SPARE | D08034J | 23 | | | | D05368J | 34 | | 150-199, 275-299 |
| 044 | 24 | PK | | | 14-1 | 27-81-21 | D08034J | 24 | | | | D05368J | 35 | | ALL |
| 045 | 24 | PK | | | 14-1 | 27-81-11 | D08034J | 25 | | | | D05368J | 36 | | ALL |
| 046 | 20 | PA | | | 31-2 | 27-62-11 | D04714P | 1 | | | | D05664P | 15 | | ALL |
| 047 | 22 | PA | | | 42-3 | SPARE | D05832P | CAP | Y | | | D05664P | CAP | Y | ALL |
| 048 | 24 | PK | | | 31-2 | 27-58-11 | D04714P | 2 | | | | D05664P | 3 | | ALL |
| 049 | 22 | PA | | | 95-3 | 27-58-11 | D04714P | 3 | | | | D04590J | 3 | | 050-099 |
| 049 | 22 | PA | | | 105-3 | 27-58-11 | D04714P | 3 | | | | D04590J | 3 | | 150-199, 275-299 |
| 050 | 24 | PK | | | 31-2 | 27-58-11 | D04714P | 4 | | | | D05664P | 5 | | ALL |
| 051 | 24 | PK | | | 31-2 | 27-58-11 | D04714P | 5 | | | | D05664P | 6 | | ALL |
| 052 | 24 | PK | | | 31-2 | 27-58-11 | D04714P | 6 | | | | D05664P | 7 | | ALL |
| 053 | 24 | PK | | | 31-2 | 27-58-11 | D04714P | 7 | | | | D05664P | 8 | | ALL |
| 054 | 24 | PK | | | 31-2 | 27-58-11 | D04714P | 8 | | | | D05664P | 9 | | ALL |
| 055 | 22 | PA | | | 31-2 | 27-51-51 | D04714P | 9 | | | | D05664P | 10 | | ALL |
| 056 | 24 | PK | | | 14-9 | 78-34-11 | D05300P | 19 | | | | D05368J | 5 | | 050-099, 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0750
Page 9
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 056 | 24 | | PK | 14-9 | 78-34-11 | D05368J | | 5 | | | D05300P | | 19 | | 275-299 |
| 057 | 24 | | PK | 21-2 | 27-51-31 | D08034J | | 3 | | | D05300P | | 12 | | ALL |
| 059 | 24 | | PK | 27-10 | 27-51-61 | D08034J | | 5 | | | D04714P | | 14 | | ALL |
| 060 | 24 | | PK | 27-10 | 27-51-61 | D08034J | | 6 | | | D04714P | | 15 | | ALL |
| 061 | 20 | | PA | 5-1 | 78-36-11 | D11830 | | 10 | | | GD00561 | D.. | 2 | | 050-099, 275-299 |
| 061 | 20 | | PA | 3-7 | 78-36-11 | D11830 | | 10 | | | GD03814 | D.. | E | *1 | 150-199 |
| 062 | 22 | | PA | 48-5 | 78-36-11 | D05300P | | 43 | | | D11830 | | 6 | | 050-099 |
| 062 | 22 | | PA | 48-5 | 78-36-11 | D11830 | | 6 | | | D05300P | | 43 | | 150-199, 275-299 |
| 063 | 24 | | PK | 27-5 | 21-31-21 | D08034J | | 41 | | | D04710P | | 38 | | ALL |
| 064 | 24 | | PK | 27-5 | 21-31-21 | D08034J | | 42 | | | D04710P | | 39 | | ALL |
| 065 | 20 | | PQ | 27-5 | 21-31-21 | D08034J | | 43 | | | D04710P | | 40 | | ALL |
| 065Z | | | BD | 0-0 | 21-31-21 | D04710P | | DED | | | D08034J | DED | | | ALL |
| 066 | 20 | | PA | 3-10 | 27-58-11 | D04590J | | 23 | | | GD00792 | A.. | 2 | | 050-099 |
| 066 | 20 | | PA | 4-3 | 27-58-11 | D04590J | | 23 | | | GD00792 | A.. | 2 | | 150-155, 162-165, 275-276 |
| 067 | 22 | | PA | 30-10 | 33-51-11 | D04710P | | 16 | | | D05664P | | 36 | | ALL |
| 068 | 20 | | PA | 36-8 | 27-62-11 | D05664P | | 45 | | | D08120P | | 21 | | ALL |
| 069 | 20 | | PA | 36-8 | 27-62-11 | D05664P | | 44 | | | D08120P | | 23 | | ALL |
| 070 | 20 | | PA | 5-1 | 78-36-11 | D11830 | | 3 | | | GD00561 | D.. | 2 | | 050-099, 275-299 |
| 070 | 20 | | PA | 3-7 | 78-36-11 | D11830 | | 3 | | | GD03814 | D.. | E | *1 | 150-199 |
| 071 | 22 | | PA | 36-8 | 27-62-11 | D05664P | | 48 | | | D08120P | | 12 | | ALL |
| 072 | 22 | | PA | 48-5 | 78-36-11 | D11830 | | 4 | | | D05300P | | 47 | | ALL |
| 073 | 22 | | PA | 36-8 | 27-62-11 | D05664P | | 47 | | | D08120P | | 14 | | ALL |
| 075 | 24 | | PK | 32-9 | 27-51-51 | D08034J | | 32 | | | D05664P | | 30 | | ALL |
| 076 | 24 | | PK | 35-3 | 27-58-11 | D05368J | | 29 | | | D05664P | | 16 | | ALL |
| 077 | 24 | | PK | 32-9 | 27-58-11 | D08034J | | 34 | | | D05664P | | 17 | | ALL |
| 078 | 22 | | PA | 100-2 | 27-58-11 | D04590J | | 1 | | | D05664P | | 13 | | 050-099 |
| 078 | 22 | | PA | 110-2 | 27-58-11 | D04590J | | 1 | | | D05664P | | 13 | | 150-155, 162-165, 275-276 |
| 079 | 22 | | PA | 100-2 | 27-58-11 | D04590J | | 2 | | | D05664P | | 14 | | 050-099 |
| 079 | 22 | | PA | 110-2 | 27-58-11 | D04590J | | 2 | | | D05664P | | 14 | | 150-155, 162-165, 275-276 |
| 080 | 24 | | PK | 42-3 | 32-09-13 | D05832P | | 27 | | | D05664P | | 33 | | ALL |
| 081 | 22 | | PA | 94-10 | 27-18-11 | D04710P | | 41 | | | D04590J | | 4 | | 050-099 |
| 081 | 22 | | PA | 104-10 | 27-18-11 | D04710P | | 41 | | | D04590J | | 4 | | 150-199, 275-299 |
| 082 | 22 | | PA | 76-8 | 27-18-11 | D05300P | | 48 | | | D04590J | | 5 | | 050-099 |
| 082 | 22 | | PA | 86-8 | 27-18-11 | D05300P | | 48 | | | D04590J | | 5 | | 150-156, 162-166 |
| 082 | 22 | | PA | 86-8 | SPARE | D05300P | | 48 | | | D04590J | | 5 | | 157, 167-199, 275-299 |
| 083 | 22 | | PA | 76-8 | 27-18-11 | D05300P | | 49 | | | D04590J | | 6 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|--------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 083 | 22 | | PA | | 86-8 | 27-18-11 | D05300P | | | | D04590J | | | | 150-156, 162-166 |
| 083 | 22 | | PA | | 86-8 | SPARE | D05300P | | | | D04590J | | | | 157, 167-199, 275-299 |
| 084 | 22 | | PA | | 94-10 | 27-18-11 | D04710P | | | | D04590J | | | | 050-099 |
| 084 | 22 | | PA | | 104-10 | 27-18-11 | D04710P | | | | D04590J | | | | 150-199, 275-299 |
| 085 | 22 | | PA | | 77-1 | 27-18-11 | D05300P | | | | SP02638 | | 9 | | 050-099 |
| 085 | 22 | | PA | | 87-4 | 27-18-11 | D05300P | | | | SP02638 | | 9 | | 150-154, 162-165, 275-276 |
| 086 | 22 | | PA | | 77-1 | 27-18-11 | D05300P | | | | SP02642 | | 9 | | 050-099 |
| 086 | 22 | | PA | | 87-4 | 27-18-11 | D05300P | | | | SP02642 | | 9 | | 150-154, 162-165, 275-276 |
| 087 | 24 | | PK | | 30-10 | 73-21-18 | D08030P | | | | D05300P | | 60 | | 050-099 |
| 087 | 24 | | PK | | 30-10 | 73-21-18 | D05300P | | | | D08030P | | 10 | | 150-199, 275-299 |
| 088 | 24 | | PK | | 30-10 | 73-21-18 | D08030P | | | | D05300P | | 61 | | 050-099 |
| 088 | 24 | | PK | | 30-10 | 73-21-18 | D05300P | | | | D08030P | | 12 | | 150-199, 275-299 |
| 089 | 20 | | PA | | 100-2 | 27-62-11 | D05664P | | | | D04590J | | 14 | | 050-099 |
| 089 | 20 | | PA | | 110-2 | 27-62-11 | D05664P | | | | D04590J | | 14 | | 150-199, 275-299 |
| 090 | 24 | | PV | DO | 67-8 | 73-21-11 | D04710P | | | | D04528J | | 2 | | 050-099 |
| 090 | 24 | | PV | DO | 77-6 | 73-21-11 | D04710P | | | | D04528J | | 2 | | 150-199 |
| 090 | 24 | | PV | AN | 77-6 | 73-21-11 | D04710P | | | | D04528J | | 2 | | 275-299 |
| 090Z | | | | DO | 0-0 | 73-21-11 | D04710P | | | FC | D04528J | =CC | D | | 050-099, 150-199 |
| 090Z | | | | AN | 0-0 | 73-21-11 | D04710P | | | FC | D04528J | =CC | D | | 275-299 |
| 091 | 24 | | PV | DP | 24-5 | 73-21-11 | D04710P | | 22 | | D08030P | | 2 | | ALL |
| 091Z | | | | DP | 0-0 | 73-21-11 | D04710P | | | FC | D08030P | | | FD | 050-099, 150-199 |
| 091Z | | | | DP | 0-0 | 73-21-11 | D04710P | | | FC | D08030P | | | FA | 275-299 |
| 092 | 24 | | PV | DQ | 24-5 | 73-21-11 | D04710P | | 17 | | D08030P | | 46 | | 050-099, 150-199 |
| 092 | 24 | | PV | CL | 24-5 | 73-21-11 | D08030P | | 46 | | D04710P | | 17 | | 275-299 |
| 092Z | | | | DQ | 0-0 | 73-21-11 | D04710P | | | FC | D08030P | | | FD | 050-099, 150-199 |
| 092Z | | | | CL | 0-0 | 73-21-11 | D04710P | | | FC | D08030P | | | FA | 275-299 |
| 093 | 16 | | PQ | AS | 37-0 | 73-21-20 | D04710P | | 47 | FL | D05832P | | 9 | FM | 050-099, 150-199 |
| 093 | 16 | | PQ | DR | 37-0 | 73-21-20 | D04710P | | 47 | FL | D05832P | | 9 | FM | 275-299 |
| 093Z | | | | AS | 0-0 | 73-21-20 | GD05398 | | S.. | E | D05832P | | | FE | 050-099 |
| 093Z | | | | AS | 0-0 | 73-21-20 | D04710P | | | | D05832P | | | FE | 150-199 |
| 093Z | | | | DR | 0-0 | 73-21-20 | GD05398 | | S.. | E | D05832P | | 29 | | 275-276 |
| 093Z | | | | DR | 0-0 | 73-21-20 | GD05398 | | S.. | E | D05832P | | | FE | 277-299 |
| 094 | 22 | | PA | | 42-3 | 78-36-11 | D05832P | | 41 | | D05664P | | 35 | | ALL |
| 095 | 24 | | PK | | 31-2 | 78-36-11 | D05664P | | 34 | | D04714P | | 40 | | 050-099 |
| 095 | 24 | | PK | | 31-2 | 78-36-11 | D04714P | | 40 | | D05664P | | 34 | | 150-199, 275-299 |
| 097 | 24 | | PK | | 13-2 | 27-81-11 | D05368J | | 1 | | D05626J | | 3 | | ALL |
| 098 | 24 | | PK | | 35-3 | 32-09-13 | D05368J | | 13 | | D05664P | | 27 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | |
| 099 | 24 | | PK | 42-3 | 78-36-11 | D05832P | 40 | | | | | | D05664P | CAP | Y | | ALL |
| 100 | 24 | | PK | 42-11 | 78-34-11 | D08120P | 9 | | | | | | D05300P | 17 | | | 050-099 |
| 100 | 24 | | PK | 42-11 | 78-34-11 | D05300P | 17 | | | | | | D08120P | 9 | | | 150-199, 275-299 |
| 101 | 24 | | PK | 42-11 | 78-34-11 | D08120P | 22 | | | | | | D05300P | 18 | | | 050-099 |
| 101 | 24 | | PK | 42-11 | 78-34-11 | D05300P | 18 | | | | | | D08120P | 22 | | | 150-199, 275-299 |
| 102 | 22 | | PA | 30-10 | 73-21-19 | D05300P | 21 | | | | | | D08030P | 14 | | | ALL |
| 103 | 20 | | PQ | EC | 30-10 | 73-21-19 | D08030P | 15 | | | | | D05300P | 22 | | | 050-099 |
| 103 | 20 | | PQ | P | 30-10 | 73-21-19 | D05300P | 22 | | | | | D08030P | 15 | | | 150-199 |
| 103 | 20 | | PQ | O | 30-10 | 73-21-19 | D05300P | 22 | | | | | D08030P | 15 | | | 275-299 |
| 103Z | | | | EC | 0-0 | 73-21-19 | D08030P | 27 | | | | | D05300P | 20 | | | 050-099 |
| 103Z | | | | P | 0-0 | 73-21-19 | D05300P | 20 | | | | | D08030P | 27 | | | 150-199 |
| 103Z | | | | O | 0-0 | 73-21-19 | D05300P | 20 | | | | | D08030P | 27 | | | 275-299 |
| 105 | 20 | | PA | | 24-5 | 73-21-19 | D04710P | 31 | | | | | D08030P | 17 | | | ALL |
| 10C | 18 | | PQ | D | 46-5 | 78-34-11 | D05300P | 40 | DK | | | | D01364 | 23 | DK | | ALL |
| 10CZ | | | | D | 0-0 | 78-34-11 | D05300P | | | FU | | | D01364 | | | FM | ALL |
| 10D | 18 | | PQ | AZ | 46-5 | 78-34-11 | D05300P | 15 | DK | | | | D01364 | 21 | DK | | ALL |
| 10DZ | | | | AZ | 0-0 | 78-34-11 | D05300P | | | FU | | | D01364 | | | FM | ALL |
| 10I | 18 | | PQ | FA | 37-0 | 78-34-21 | D04710P | 54 | DL | | | | D05832P | 23 | DK | | ALL |
| 10IZ | | | | FA | 0-0 | 78-34-21 | D04710P | | | FO | | | D05832P | | | FV | ALL |
| 10L | 18 | | PQ | Q | 37-0 | 78-34-11 | D04710P | 51 | DL | | | | D05832P | 39 | DK | | ALL |
| 10LZ | | | | Q | 0-0 | 78-34-11 | D04710P | 25 | | | | | D05832P | | | FV | ALL |
| 10N | 18 | | PQ | BA | 37-0 | 78-34-21 | D04710P | 43 | DL | | | | D05832P | 26 | DK | | ALL |
| 10NZ | | | | BA | 0-0 | 78-34-21 | D04710P | | | FO | | | D05832P | | | FV | ALL |
| 111 | 22 | | PA | | 42-3 | 76-11-11 | D05832P | 32 | | | | | D05664P | 39 | | | ALL |
| 112 | 22 | | PQ | CT | 30-10 | 29-11-22 | D04710P | 37 | | | | | D05664P | 42 | | | 050-099 |
| 112 | 22 | | PQ | EL | 30-10 | 29-11-22 | D04710P | 37 | | | | | D05664P | 42 | | | 150-199, 275-299 |
| 112Z | | | | CT | 0-0 | 29-11-22 | D04710P | DED | | | | | D05664P | DED | | | 050-099 |
| 112Z | | | | EL | 0-0 | 29-11-22 | D04710P | DED | | | | | D05664P | DED | | | 150-199, 275-299 |
| 115 | 22 | | PA | | 26-6 | 27-58-31 | D04710P | 9 | | | | | D05626J | 4 | | | ALL |
| 116 | 24 | | PK | | 20-3 | 27-81-31 | D05300P | 11 | | | | | D05626J | 5 | | | ALL |
| 118 | 24 | | PK | | 26-6 | 27-51-11 | D04710P | 12 | | | | | D05626J | 7 | | | ALL |
| 121 | 20 | | PA | | 4-5 | 27-13-11 | D04402J | 1 | | | | | GD00432 | D.. | 2 | | ALL |
| 122 | 20 | | PA | | 4-5 | 27-13-11 | D04402J | 4 | | | | | GD00432 | D.. | 2 | | ALL |
| 125 | 22 | | PA | | 99-3 | 27-13-11 | D04402J | 5 | | | | | D04714P | 24 | | | 050-099 |
| 125 | 22 | | PA | | 109-7 | 27-13-11 | D04402J | 5 | | | | | D04714P | 24 | | | 150-199, 275-299 |
| 127 | 24 | | PK | | 37-5 | 27-38-11 | D05300P | 31 | | | | | D04714P | 16 | | | ALL |
| 131 | 24 | | PK | | 37-1 | 27-28-11 | D05300P | 1 | | | | | D04710P | 1 | | | ALL |
| 134 | 24 | | PK | | 37-1 | 27-28-13 | D05300P | 4 | | | | | D04710P | 4 | | | ALL |
| 142 | 20 | | PA | | 43-8 | 27-21-11 | D05300P | 6 | | | | | D01830 | 14 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 143 | 20 | PQ | BM | | 11-1 | 27-21-11 | TB0031F | A022 | 2 | | D01830 | | 6 | | ALL |
| 143Z | | | BM | | 0-0 | 27-21-11 | TB0031F | DED | | | D01830 | | DED | | ALL |
| 144 | 24 | PK | | | 43-5 | 27-28-13 | D05300P | | 8 | | D01832 | | 3 | | ALL |
| 145 | 20 | PA | | | 8-7 | 27-28-13 | GD02464 | A.. | 2 | | D01832 | | 4 | | ALL |
| 146 | 20 | PQ | BN | | 20-1 | 27-21-11 | D04714P | | 22 | | D01830 | | 11 | | ALL |
| 146Z | | | BN | | 0-0 | 27-21-11 | D04714P | DED | | | D01830 | | DED | | ALL |
| 147 | 24 | PK | | | 30-5 | 31-31-22 | D08016P | | 6 | | D05370J | | 27 | | ALL |
| 148 | 24 | PK | | | 37-1 | SPARE | D05300P | | 33 | | D04710P | | 7 | | 050-099 |
| 148 | 24 | PK | | | 37-1 | SPARE | D04710P | | 7 | | D05300P | | 33 | | 150-199, 275-299 |
| 149 | 24 | PK | | | 37-1 | SPARE | D05300P | | 34 | | D04710P | | 8 | | 050-099 |
| 149 | 24 | PK | | | 37-1 | SPARE | D04710P | | 8 | | D05300P | | 34 | | 150-199, 275-299 |
| 150 | 18 | PA | | | 36-6 | 27-11-11 | D05368J | | 21 | | D01830 | | 9 | | ALL |
| 151 | 18 | PA | | | 36-6 | 27-11-11 | D05368J | | 23 | | D01830 | | 5 | | ALL |
| 158 | 22 | PA | | | 30-8 | 73-21-19 | D08030P | | 31 | | D05832P | | 13 | | ALL |
| 159 | 22 | PA | | | 30-8 | 73-21-19 | D08030P | | 32 | | D05832P | | 15 | | ALL |
| 161 | 20 | PA | | | 5-3 | 33-13-18 | SP02272 | | | 9 | D01830 | | 1 | | 050-099, 150-155, 162-165, 275-276 |
| 162 | 20 | PA | | | 2-2 | 33-13-18 | GD04472 | A.. | 2 | | D01830 | | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 167 | 24 | PK | | | 29-8 | 73-21-12 | D08030P | | 33 | | D05664P | | 28 | | ALL |
| 168 | 24 | PK | | | 24-5 | SPARE | D08030P | | 34 | | D04710P | | 49 | | 150-199 |
| 168 | 24 | PK | | | 24-5 | 73-21-16 | D08030P | | 34 | | D04710P | | 49 | | 275-299 |
| 169 | 22 | PA | | | 31-2 | 27-62-11 | D04714P | | 10 | | D05664P | | 22 | | ALL |
| 170 | 24 | PK | | | 30-8 | 73-21-17 | D08030P | | 36 | | D05832P | | 11 | | ALL |
| 171 | 24 | PK | | | 30-8 | 73-21-17 | D08030P | | 37 | | D05832P | | 12 | | ALL |
| 172 | 24 | PK | | | 37-1 | 78-34-11 | D04710P | | 50 | | D05300P | | 35 | | 050-099 |
| 172 | 24 | PK | | | 37-1 | 78-34-11 | D05300P | | 35 | | D04710P | | 50 | | 150-199, 275-299 |
| 176 | 24 | PK | | | 24-5 | SPARE | D04710P | CAP | Y | | D08030P | | 28 | | 050-099, 150-199 |
| 176 | 24 | PK | | | 24-5 | SPARE | D04710P | | 45 | | D08030P | | 28 | | 275-299 |
| 177 | 24 | PK | | | 24-5 | 27-58-21 | D04710P | | 48 | | D08030P | | 29 | | ALL |
| 180 | 20 | PA | | | 68-0 | SPARE | D04528J | | 29 | | D04714P | CAP | Y | | 050-099 |
| 180 | 20 | PA | | | 77-11 | SPARE | D04528J | | 29 | | D04714P | CAP | Y | | 150-199, 275-299 |
| 181 | 20 | PA | | | 68-0 | SPARE | D04528J | | 30 | | D04714P | CAP | Y | | 050-099 |
| 181 | 20 | PA | | | 77-11 | SPARE | D04528J | CAP | Y | | D04714P | CAP | Y | | 150-199, 277-299 |
| 181 | 20 | PA | | | 77-11 | SPARE | D04528J | | 30 | | D04714P | CAP | Y | | 275-276 |
| 182 | 20 | PA | | | 68-0 | SPARE | D04528J | | 31 | | D04714P | | 38 | | 050-099 |
| 182 | 20 | PA | | | 77-11 | SPARE | D04528J | CAP | Y | | D04714P | | 38 | | 150-199, 277-299 |
| 182 | 20 | PA | | | 77-11 | SPARE | D04528J | | 31 | | D04714P | | 38 | | 275-276 |
| 183 | 20 | PA | | | 68-2 | SPARE | D04486J | | 23 | | D04714P | | 39 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 183 | 20 | | PA | | 77-10 | SPARE | D04486J | 23 | | | D04714P | 39 | | | 150-199, 275-299 |
| 184 | 20 | | PA | | 67-9 | SPARE | D04486J | CAP | Y | | D04710P | CAP | Y | | 050-099 |
| 184 | 20 | | PA | | 77-5 | SPARE | D04486J | CAP | Y | | D04710P | CAP | Y | | 150-199, 275-299 |
| 185 | 20 | | PA | | 67-9 | SPARE | D04486J | CAP | Y | | D04710P | 52 | | | 050-099 |
| 186 | 20 | | PA | | 67-9 | SPARE | D04486J | CAP | Y | | D04710P | 53 | | | 050-099 |
| 186 | 20 | | PA | | 77-5 | SPARE | D04486J | CAP | Y | | D04710P | 53 | | | 150-199, 275-299 |
| 187 | 20 | | PA | | 67-9 | SPARE | D04486J | 29 | | | D04710P | CAP | Y | | 050-099 |
| 187 | 20 | | PA | | 77-5 | SPARE | D04486J | 29 | | | D04710P | CAP | Y | | 150-199, 275-299 |
| 188 | 20 | | PA | | 67-9 | SPARE | D04486J | 30 | | | D04710P | 55 | | | 050-099 |
| 188 | 20 | | PA | | 77-5 | SPARE | D04486J | 30 | | | D04710P | 55 | | | 150-199, 275-299 |
| 189 | 20 | | PA | | 68-2 | SPARE | D04486J | CAP | Y | | D04714P | CAP | Y | | 050-099 |
| 189 | 20 | | PA | | 77-10 | SPARE | D04486J | CAP | Y | | D04714P | CAP | Y | | 150-199, 275-299 |
| 195 | 22 | | PA | | 42-10 | 28-22-21 | D08120P | 11 | | | D05832P | 24 | | | ALL |
| 199 | 20 | | PQ | HX | 49-0 | 73-21-19 | D04528J | 40 | | | D05300P | 7 | | | 050-099 |
| 199 | 20 | | PQ | RT | 59-4 | 73-21-19 | D04528J | 40 | | | D05300P | 7 | | | 150-199 |
| 199 | 20 | | PQ | HX | 59-4 | 73-21-19 | D05300P | 7 | | | D04528J | 40 | | | 275-299 |
| 199Z | | | | HX | 0-0 | 73-21-19 | D05300P | 5 | | | D04528J | =CC | D | | 050-099, 275-299 |
| 199Z | | | | RT | 0-0 | 73-21-19 | D04528J | =CC | D | | D05300P | 5 | | | 150-199 |
| 201B | 24 | | PW | AL | 79-4 | 73-21-13 | D05964J | 11 | | | D04528J | 15 | | | 050-099 |
| 201B | 24 | | PW | AL | 89-3 | 73-21-13 | D05964J | 11 | | | D04528J | 15 | | | 150-199, 275-276 |
| 201B | 24 | | PW | IA | 89-3 | 73-21-13 | D05964J | 11 | | | D04528J | 15 | | | 277-299 |
| 201R | 24 | | PW | AL | 0-0 | 73-21-13 | D05964J | 12 | | | D04528J | 16 | | | 050-099, 150-199, 275-276 |
| 201R | 24 | | PW | IA | 0-0 | 73-21-13 | D05964J | 12 | | | D04528J | 16 | | | 277-299 |
| 201Z | | | | AL | 0-0 | 73-21-13 | D05964J | | | FX | D04528J | =CC | D | | 050-099, 157, 167-199 |
| 201Z | | | | AL | 0-0 | 73-21-13 | D05964J | | | FA | D04528J | =CC | D | | 150-156, 162-166 |
| 201Z | | | | AL | 0-0 | 73-21-13 | D05964J | | | FE | D04528J | =CC | D | | 275-276 |
| 201Z | | | | IA | 0-0 | 73-21-13 | D05964J | | | FX | D04528J | =CC | D | | 277-299 |
| 205B | 24 | | PW | IE | 49-0 | 73-21-14 | D05300P | 36 | | | D04528J | 23 | | | 050-099 |
| 205B | 24 | | PW | AK | 59-4 | 73-21-14 | D05300P | 36 | | | D04528J | 23 | | | 150-199 |
| 205B | 24 | | PW | IE | 59-4 | 73-21-14 | D05300P | 36 | | | D04528J | 23 | | | 275-299 |
| 205R | 24 | | PW | IE | 0-0 | 73-21-14 | D05300P | 37 | | | D04528J | 24 | | | 050-099, 275-299 |
| 205R | 24 | | PW | AK | 0-0 | 73-21-14 | D05300P | 37 | | | D04528J | 24 | | | 150-199 |
| 205Z | | | | IE | 0-0 | 73-21-14 | D05300P | 39 | | | D04528J | =CC | D | | 050-099, 275-299 |
| 205Z | | | | AK | 0-0 | 73-21-14 | D05300P | 39 | | | D04528J | =CC | D | | 150-199 |
| 206B | 24 | | PW | LL | 21-1 | 73-21-14 | D08034J | 44 | | | D05832P | 3 | | | 050-099 |
| 206B | 24 | | PW | BR | 21-1 | 73-21-14 | D05832P | 3 | | | D08034J | 44 | | | 150-199 |
| 206B | 24 | | PW | BR | 21-1 | 73-21-14 | D08034J | 44 | | | D05832P | 3 | | | 275-299 |
| 206R | 24 | | PW | LL | 0-0 | 73-21-14 | D08034J | 45 | | | D05832P | 4 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | |
| 206R | 24 | PW | BR | 0-0 | 73-21-14 | D05832P | | 4 | | | | | D08034J | 45 | | | 150-199 |
| 206R | 24 | PW | BR | 0-0 | 73-21-14 | D08034J | | 45 | | | | | D05832P | 4 | | | 275-299 |
| 206Z | | | LL | 0-0 | 73-21-14 | D08034J | | | | | FL | | D05832P | 43 | | | 050-099 |
| 206Z | | | BR | 0-0 | 73-21-14 | D05832P | | 43 | | | | | D08034J | | FL | | 150-199 |
| 206Z | | | BR | 0-0 | 73-21-14 | D08034J | | | | | FG | | D05832P | 43 | | | 275-299 |
| 207B | 24 | PW | LM | 51-9 | 73-21-14 | D08034J | | 46 | | | | | D04528J | 19 | | | 050-099 |
| 207B | 24 | PW | BC | 61-7 | 73-21-14 | D08034J | | 46 | | | | | D04528J | 19 | | | 150-199 |
| 207B | 24 | PW | BS | 61-7 | 73-21-14 | D08034J | | 46 | | | | | D04528J | 19 | | | 275-276, 280-299 |
| 207B | 24 | PW | IG | 61-7 | 73-21-14 | D08034J | | 46 | | | | | D04528J | 19 | | | 277-278 |
| 207R | 24 | PW | LM | 0-0 | 73-21-14 | D08034J | | 47 | | | | | D04528J | 20 | | | 050-099 |
| 207R | 24 | PW | BC | 0-0 | 73-21-14 | D08034J | | 47 | | | | | D04528J | 20 | | | 150-199 |
| 207R | 24 | PW | BS | 0-0 | 73-21-14 | D08034J | | 47 | | | | | D04528J | 20 | | | 275-276, 280-299 |
| 207R | 24 | PW | IG | 0-0 | 73-21-14 | D08034J | | 47 | | | | | D04528J | 20 | | | 277-278 |
| 207Z | | | LM | 0-0 | 73-21-14 | D08034J | | | | | FL | | D04528J | =CC | D | | 050-099 |
| 207Z | | | BC | 0-0 | 73-21-14 | D08034J | | | | | FL | | D04528J | =CC | D | | 150-199 |
| 207Z | | | BS | 0-0 | 73-21-14 | D08034J | | | | | FG | | D04528J | =CC | D | | 275-276, 280-299 |
| 207Z | | | IG | 0-0 | 73-21-14 | D08034J | | | | | FG | | D04528J | =CC | D | | 277-278 |
| 208B | 22 | PB | AE | 78-0 | 27-51-41 | D04610J | | 1 | | | | | D05626J | 20 | | | 050-099 |
| 208B | 22 | PB | AE | 88-0 | 27-51-41 | D04610J | | 1 | | | | | D05626J | 20 | | | 150-199, 275-299 |
| 208R | 22 | PB | AE | 0-0 | 27-51-41 | D04610J | | 2 | | | | | D05626J | 21 | | | ALL |
| 209B | 24 | PL | M | 44-10 | 27-88-12 | D05370J | | 1 | | | | | D04486J | 1 | | | 050-099 |
| 209B | 24 | PL | M | 55-0 | 27-88-12 | D05370J | | 1 | | | | | D04486J | 1 | | | 150-199, 275-299 |
| 209R | 24 | PL | M | 0-0 | 27-88-12 | D05370J | | 2 | | | | | D04486J | 2 | | | ALL |
| 210B | 24 | PL | N | 44-10 | 27-88-12 | D05370J | | 3 | | | | | D04486J | 3 | | | 050-099 |
| 210B | 24 | PL | N | 55-0 | 27-88-12 | D05370J | | 3 | | | | | D04486J | 3 | | | 150-199, 275-299 |
| 210R | 24 | PL | N | 0-0 | 27-88-12 | D05370J | | 4 | | | | | D04486J | 4 | | | ALL |
| 211B | 24 | PL | BF | 44-10 | 27-88-12 | D05370J | | 5 | | | | | D04486J | 5 | | | 050-099 |
| 211B | 24 | PL | BF | 55-0 | 27-88-12 | D05370J | | 5 | | | | | D04486J | 5 | | | 150-199, 275-299 |
| 211R | 24 | PL | BF | 0-0 | 27-88-12 | D05370J | | 6 | | | | | D04486J | 6 | | | ALL |
| 212B | 24 | PL | P | 44-10 | 27-88-12 | D05370J | | 7 | | | | | D04486J | 7 | | | 050-099 |
| 212B | 24 | PL | BH | 55-0 | 27-88-12 | D05370J | | 7 | | | | | D04486J | 7 | | | 150-199 |
| 212B | 24 | PL | P | 55-0 | 27-88-12 | D05370J | | 7 | | | | | D04486J | 7 | | | 275-299 |
| 212R | 24 | PL | P | 0-0 | 27-88-12 | D05370J | | 8 | | | | | D04486J | 8 | | | 050-099, 275-299 |
| 212R | 24 | PL | BH | 0-0 | 27-88-12 | D05370J | | 8 | | | | | D04486J | 8 | | | 150-199 |
| 213B | 24 | PL | S | 44-10 | 27-88-12 | D05370J | | 9 | | | | | D04486J | 9 | | | 050-099 |
| 213B | 24 | PL | S | 55-0 | 27-88-12 | D05370J | | 9 | | | | | D04486J | 9 | | | 150-199, 275-299 |
| 213R | 24 | PL | S | 0-0 | 27-88-12 | D05370J | | 10 | | | | | D04486J | 10 | | | ALL |
| 214B | 24 | PL | T | 44-10 | 27-88-12 | D05370J | | 11 | | | | | D04486J | 11 | | | 050-099 |
| 214B | 24 | PL | T | 55-0 | 27-88-12 | D05370J | | 11 | | | | | D04486J | 11 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|----|--|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | | | |
| 214R | 24 | PL | T | 0-0 | 27-88-12 | D05370J | | | | | 12 | | | | D04486J | 12 | | | ALL |
| 215B | 24 | PL | U | 44-10 | 27-88-12 | D05370J | | | | | 13 | | | | D04486J | 13 | | | 050-099 |
| 215B | 24 | PL | U | 55-0 | 27-88-12 | D05370J | | | | | 13 | | | | D04486J | 13 | | | 150-199, 275-299 |
| 215R | 24 | PL | U | 0-0 | 27-88-12 | D05370J | | | | | 14 | | | | D04486J | 14 | | | ALL |
| 216B | 24 | PL | V | 44-10 | 27-88-12 | D05370J | | | | | 15 | | | | D04486J | 15 | | | 050-099 |
| 216B | 24 | PL | V | 55-0 | 27-88-12 | D05370J | | | | | 15 | | | | D04486J | 15 | | | 150-199, 275-299 |
| 216R | 24 | PL | V | 0-0 | 27-88-12 | D05370J | | | | | 16 | | | | D04486J | 16 | | | ALL |
| 217B | 24 | PL | W | 44-10 | 27-88-12 | D05370J | | | | | 17 | | | | D04486J | 17 | | | 050-099 |
| 217B | 24 | PL | W | 55-0 | 27-88-12 | D05370J | | | | | 17 | | | | D04486J | 17 | | | 150-199, 275-299 |
| 217R | 24 | PL | W | 0-0 | 27-88-12 | D05370J | | | | | 18 | | | | D04486J | 18 | | | ALL |
| 218B | 24 | PL | X | 44-10 | 27-88-12 | D05370J | | | | | 19 | | | | D04486J | 19 | | | 050-099 |
| 218B | 24 | PL | X | 55-0 | 27-88-12 | D05370J | | | | | 19 | | | | D04486J | 19 | | | 150-199, 275-299 |
| 218R | 24 | PL | X | 0-0 | 27-88-12 | D05370J | | | | | 20 | | | | D04486J | 20 | | | ALL |
| 219B | 24 | PL | Y | 44-10 | 27-88-12 | D05370J | | | | | 21 | | | | D04486J | 21 | | | 050-099 |
| 219B | 24 | PL | Y | 55-0 | 27-88-12 | D05370J | | | | | 21 | | | | D04486J | 21 | | | 150-199, 275-299 |
| 219R | 24 | PL | Y | 0-0 | 27-88-12 | D05370J | | | | | 22 | | | | D04486J | 22 | | | ALL |
| 220B | 24 | PL | Z | 44-10 | 27-88-12 | D05370J | | | | | 25 | | | | D04486J | 25 | | | 050-099 |
| 220B | 24 | PL | Z | 55-0 | 27-88-12 | D05370J | | | | | 25 | | | | D04486J | 25 | | | 150-199, 275-299 |
| 220R | 24 | PL | Z | 0-0 | 27-88-12 | D05370J | | | | | 26 | | | | D04486J | 26 | | | ALL |
| 222B | 22 | PB | E | 33-3 | 27-51-31 | D08034J | | | | | 8 | | | | D08120P | 25 | | | ALL |
| 222R | 22 | PB | E | 0-0 | 27-51-31 | D08034J | | | | | 9 | | | | D08120P | 26 | | | ALL |
| 223B | 24 | PL | G | 33-3 | 27-58-31 | D08034J | | | | | 13 | | | | D08120P | 30 | | | ALL |
| 223R | 24 | PL | G | 0-0 | 27-58-31 | D08034J | | | | | 14 | | | | D08120P | 31 | | | ALL |
| 224B | 24 | PL | J | 21-2 | 27-51-31 | D08034J | | | | | 28 | | | | D08030P | 18 | | | ALL |
| 224R | 24 | PL | J | 0-0 | 27-51-31 | D08034J | | | | | 29 | | | | D08030P | 19 | | | ALL |
| 225B | 24 | PL | K | 21-2 | 27-58-31 | D08034J | | | | | 30 | | | | D08030P | 20 | | | ALL |
| 225R | 24 | PL | K | 0-0 | 27-58-31 | D08034J | | | | | 31 | | | | D08030P | 21 | | | ALL |
| 226B | 22 | PB | AC | 88-7 | 27-58-21 | D04590J | | | | | 15 | | | | D08030P | 22 | | | 050-099 |
| 226B | 22 | PB | AC | 98-7 | 27-58-21 | D04590J | | | | | 15 | | | | D08030P | 22 | | | 150-199, 275-299 |
| 226R | 22 | PB | AC | 0-0 | 27-58-21 | D04590J | | | | | 16 | | | | D08030P | 23 | | | ALL |
| 227B | 22 | PB | AA | 50-4 | 27-81-31 | D04532J | | | | | 1 | | | | D05626J | 15 | | | 050-099 |
| 227B | 22 | PB | AA | 60-7 | 27-81-31 | D04532J | | | | | 1 | | | | D05626J | 15 | | | 150-199, 275-299 |
| 227R | 22 | PB | AA | 0-0 | 27-81-31 | D04532J | | | | | 2 | | | | D05626J | 16 | | | ALL |
| 231B | 22 | PB | B | 20-3 | 27-51-41 | D05300P | | | | | 24 | | | | D05626J | 9 | | | ALL |
| 231R | 22 | PB | B | 0-0 | 27-51-41 | D05300P | | | | | 25 | | | | D05626J | 10 | | | ALL |
| 233B | 24 | PL | A | 43-5 | 27-28-13 | D05300P | | | | | 10 | | | | D01832 | 10 | | | ALL |
| 233R | 24 | PL | A | 0-0 | 27-28-13 | D05300P | | | | | 9 | | | | D01832 | 9 | | | ALL |
| 235R | 20 | RJ | I | 14-1 | 77-31-11 | D08034J | | | | | 50 | | | | D05368J | 37 | | | ALL |
| 235W | 20 | RJ | I | 0-0 | 77-31-11 | D08034J | | | | | 51 | | | | D05368J | 38 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|--|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | | |
| 235Z | | | I | 0-0 | 77-31-11 | D08034J | | 52 | | | | | D05368J | | 39 | | | ALL |
| 237B | 20 | PR | BL | 99-3 | 27-13-11 | D04402J | | 2 | | | | | D04714P | | 28 | | | 050-099 |
| 237B | 20 | PR | BL | 109-7 | 27-13-11 | D04402J | | 2 | | | | | D04714P | | 28 | | | 150-199, 275-299 |
| 237R | 20 | PR | BL | 0-0 | 27-13-11 | D04402J | | 3 | | | | | D04714P | | 27 | | | ALL |
| 237Z | | | BL | 0-0 | 27-13-11 | D04402J | | | DED | | | | D04714P | | DED | | | ALL |
| 239B | 24 | PW | AK | 61-5 | 73-21-17 | D08030P | | 4 | | | | | D04528J | | 9 | | | 050-099 |
| 239B | 24 | PW | AQ | 71-3 | 73-21-17 | D08030P | | 4 | | | | | D04528J | | 9 | | | 150-199 |
| 239B | 24 | PW | JN | 71-3 | 73-21-17 | D08030P | | 4 | | | | | D04528J | | 9 | | | 275-299 |
| 239R | 24 | PW | AK | 0-0 | 73-21-12 | D08030P | | 6 | | | | | D04528J | | 12 | | | 050-099 |
| 239R | 24 | PW | AQ | 0-0 | 73-21-12 | D08030P | | 6 | | | | | D04528J | | 12 | | | 150-199 |
| 239R | 24 | PW | JN | 0-0 | 73-21-12 | D08030P | | 6 | | | | | D04528J | | 12 | | | 275-299 |
| 239Z | | | AK | 0-0 | 73-21-12 | D08030P | | | | | FI | | D04528J | =CC | D | | | 050-099 |
| 239Z | | | AQ | 0-0 | 73-21-17 | D08030P | | | | | FF | | D04528J | =CC | M | | | 150-156, 162-166 |
| 239Z | | | AQ | 0-0 | 73-21-17 | D08030P | | | | | FF | | D04528J | =CC | D | | | 157, 167-199 |
| 239Z | | | JN | 0-0 | 73-21-12 | D08030P | | | | | FI | | D04528J | =CC | L | | | 275-276 |
| 239Z | | | JN | 0-0 | 73-21-12 | D08030P | | | | | FI | | D04528J | =CC | D | | | 277-299 |
| 240B | 24 | PW | JO | 21-2 | 77-31-11 | D08034J | | 27 | | | | | D05300P | | 54 | | | 050-099, 275-299 |
| 240B | 24 | PW | AU | 21-2 | 77-31-11 | D08034J | | 27 | | | | | D05300P | | 54 | | | 150-199 |
| 240R | 24 | PW | JO | 0-0 | 77-31-11 | D08034J | | 26 | | | | | D05300P | | 53 | | | 050-099, 275-299 |
| 240R | 24 | PW | AU | 0-0 | 77-31-11 | D08034J | | 26 | | | | | D05300P | | 53 | | | 150-199 |
| 240Z | | | JO | 0-0 | 77-31-11 | D08034J | | 2 | | | | | D05300P | | 55 | | | 050-099, 277-299 |
| 240Z | | | AU | 0-0 | 77-31-11 | D08034J | | 2 | | | | | D05300P | | 55 | | | 150-199 |
| 240Z | | | JO | 0-0 | 77-31-11 | D08034J | | 2 | | | | | D05300P | | 58 | | | 275-276 |
| 244B | 18 | 5D | CP | 95-3 | 28-43-11 | D04590J | | 10 | | | | | D04714P | | 11 | DL | | 050-099 |
| 244B | 18 | 5D | CP | 105-3 | 28-43-11 | D04590J | | 10 | | | | | D04714P | | 11 | DL | | 150-199, 275-299 |
| 244R | 18 | 5D | CP | 0-0 | 28-43-11 | D04590J | | 11 | | | | | D04714P | | 12 | DL | | ALL |
| 245B | 24 | PW | BQ | 61-5 | 77-12-12 | D08030P | | 40 | | | | | D04528J | | 36 | | | 050-099 |
| 245B | 24 | PW | BQ | 71-3 | 77-12-12 | D08030P | | 40 | | | | | D04528J | | 36 | | | 150-199, 275-276, 280-299 |
| 245B | 24 | PW | JT | 71-3 | 77-12-12 | D08030P | | 40 | | | | | D04528J | | 36 | | | 277-278 |
| 245R | 24 | PW | BQ | 0-0 | 77-12-12 | D08030P | | 38 | | | | | D04528J | | 35 | | | 050-099, 150-199, 275-276, 280-299 |
| 245R | 24 | PW | JT | 0-0 | 77-12-12 | D08030P | | 38 | | | | | D04528J | | 35 | | | 277-278 |
| 245Z | | | BQ | 0-0 | 77-12-12 | D08030P | | 39 | | | | | D04528J | =CC | D | | | 050-099, 157, 167-199, 280-299 |
| 245Z | | | BQ | 0-0 | 77-12-12 | D08030P | | 39 | | | | | D04528J | =CC | M | | | 150-156, 162-166 |
| 245Z | | | BQ | 0-0 | 77-12-12 | D08030P | | 39 | | | | | D04528J | =CC | L | | | 275-276 |
| 245Z | | | JT | 0-0 | 77-12-12 | D08030P | | 39 | | | | | D04528J | =CC | D | | | 277-278 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 17

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | |
| 249 | 22 | | PA | 65-0 | 27-89-11 | D04486J | | 42 | | | | | D05832P | 52 | | | 050-099, 150-199, 275-278 |
| 249 | 22 | | PA | 56-0 | 27-89-11 | D04486J | | 42 | | | | | D05832P | 52 | | | 280-299 |
| 271 | 20 | | PA | 5-0 | 27-89-11 | D04486J | | 43 | | | | | GD03554 | D.. | 2 | | ALL |
| 285B | 24 | | PW LJ | 13-11 | 77-31-11 | D08034J | | 54 | | | | | D05370J | 38 | | | 050-099, 275-299 |
| 285B | 24 | | PW JM | 13-11 | 77-31-11 | D08034J | | 54 | | | | | D05370J | 38 | | | 150-199 |
| 285R | 24 | | PW LJ | 0-0 | 77-31-11 | D08034J | | 53 | | | | | D05370J | 37 | | | 050-099, 275-299 |
| 285R | 24 | | PW JM | 0-0 | 77-31-11 | D08034J | | 53 | | | | | D05370J | 37 | | | 150-199 |
| 285Z | | | LJ | 0-0 | 77-31-11 | D08034J | | 49 | | | | | D05370J | 39 | | | 050-099, 275-299 |
| 285Z | | | JM | 0-0 | 77-31-11 | D08034J | | 49 | | | | | D05370J | 39 | | | 150-199 |
| 290B | 20 | | PB LO | 7-0 | 33-13-18 | SP04098 | | | 9 | | | | D01830 | 2 | | | 156-157, 166-199 |
| 290B | 20 | | PB AP | 7-0 | 33-13-18 | SP04098 | | | 9 | | | | D01830 | 2 | | | 277-299 |
| 290R | 20 | | PB LO | 0-0 | 33-13-18 | SP02272 | | | 9 | | | | D01830 | 1 | | | 156-157, 166-199 |
| 290R | 20 | | PB AP | 0-0 | 33-13-18 | SP02272 | | | 9 | | | | D01830 | 1 | | | 277-299 |
| 291B | 20 | | PB LP | 7-0 | 33-13-18 | SP04098 | | | 9 | | | | D01832 | 2 | | | 156-157, 166-199 |
| 291B | 20 | | PB AQ | 7-0 | 33-13-18 | SP04098 | | | 9 | | | | D01832 | 2 | | | 277-299 |
| 291R | 20 | | PB LP | 0-0 | 33-13-18 | SP02272 | | | 9 | | | | D01832 | 1 | | | 156-157, 166-199 |
| 291R | 20 | | PB AQ | 0-0 | 33-13-18 | SP02272 | | | 9 | | | | D01832 | 1 | | | 277-299 |
| 293 | 24 | | PK | 42-3 | 30-81-11 | D05832P | | 51 | | | | | D05664P | 43 | | | 050-099, 150-154, 156-157, 166-199 |
| 294B | 24 | | PW LS | 63-0 | 31-35-14 | D04791J | | 14 | | | | | D04528J | 30 | | | 277 |
| 294R | 24 | | PW LS | 0-0 | 31-35-14 | D04791J | | 13 | | | | | D04528J | 31 | | | 277 |
| 294Z | | | LS | 0-0 | 31-35-14 | D04791J | | | | | FB | | D04528J | | | FW | 277 |
| 297B | 18 | | VG BJ | 73-0 | 78-36-11 | D04486J | | 28 | DK | | | | D05664P | CAP | Y | | 050-099 |
| 297B | 18 | | VG BJ | 82-9 | 78-36-11 | D04486J | | 28 | DK | | | | D05664P | CAP | Y | | 150-199 |
| 297B | 18 | | VG BJ | 82-9 | 78-36-11 | D04486J | | 28 | DK | | | | D05664P | 38 | DK | | 275-299 |
| 297R | 18 | | VG BJ | 0-0 | 78-36-11 | D04486J | | 36 | DK | | | | D05664P | CAP | Y | | 050-099, 150-199 |
| 297R | 18 | | VG BJ | 0-0 | 78-36-11 | D04486J | | 36 | DK | | | | D05664P | 37 | DK | | 275-299 |
| 297Z | | | BJ | 0-0 | 78-36-11 | D04486J | | =CC | D | | | | D05664P | DED | | | 050-099, 150-199 |
| 297Z | | | BJ | 0-0 | 78-36-11 | D04486J | | =CC | D | | | | D05664P | | | FP | 275-299 |
| 298B | 18 | | VG BI | 73-0 | 78-36-11 | D05664P | | CAP | Y | | | | D04486J | 38 | DK | | 050-099 |
| 298B | 18 | | VG BI | 82-9 | 78-36-11 | D05664P | | CAP | Y | | | | D04486J | 38 | DK | | 150-199 |
| 298B | 18 | | VG BI | 82-9 | 78-36-11 | D05664P | | 26 | DK | | | | D04486J | 38 | DK | | 275-299 |
| 298R | 18 | | VG BI | 0-0 | 78-36-11 | D05664P | | CAP | Y | | | | D04486J | 31 | DK | | 050-099, 150-199 |
| 298R | 18 | | VG BI | 0-0 | 78-36-11 | D05664P | | 24 | DK | | | | D04486J | 31 | DK | | 275-299 |
| 298Z | | | BI | 0-0 | 78-36-11 | D05664P | | DED | | | | | D04486J | =CC | D | | 050-099, 150-199 |
| 298Z | | | BI | 0-0 | 78-36-11 | D05664P | | | | | FP | | D04486J | =CC | D | | 275-299 |
| 300B | 18 | | PS LY | 78-0 | 31-31-25 | D04590J | | 13 | | | | | D05626J | 44 | DK | | 050-099 |
| 300B | 18 | | VH LY | 88-0 | 31-31-25 | D04590J | | 13 | | | | | D05626J | 44 | DK | | 150-152 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 18

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 300B | 18 | PS | LY | 88-0 | 31-31-25 | D04590J | | 13 | | | D05626J | 44 | DK | | 153-199, 275-299 |
| 300R | 18 | PS | LY | 0-0 | 31-31-25 | D04590J | | 9 | | | D05626J | 41 | DK | | 050-099, 153-199, 275-299 |
| 300R | 18 | VH | LY | 0-0 | 31-31-25 | D04590J | | 9 | | | D05626J | 41 | DK | | 150-152 |
| 300Y | 18 | PS | LY | 0-0 | 31-31-25 | D04590J | | 12 | | | D05626J | 42 | DK | | 050-099, 153-199, 275-299 |
| 300Y | 18 | VH | LY | 0-0 | 31-31-25 | D04590J | | 12 | | | D05626J | 42 | DK | | 150-152 |
| 300Z | | | LY | 0-0 | 31-31-25 | D04590J | | 8 | | | D05626J | 43 | | | ALL |
| 302B | 24 | PX | AM | 79-4 | 73-21-13 | D05964J | | 7 | | | D04528J | 27 | | | 050-099 |
| 302B | 24 | PX | AM | 89-3 | 73-21-13 | D05964J | | 7 | | | D04528J | 27 | | | 150-199, 275-276 |
| 302B | 24 | PX | MB | 89-3 | 73-21-13 | D05964J | | 7 | | | D04528J | 27 | | | 277-299 |
| 302R | 24 | PX | AM | 0-0 | 73-21-13 | D05964J | | 8 | | | D04528J | 26 | | | 050-099, 150-199, 275-276 |
| 302R | 24 | PX | MB | 0-0 | 73-21-13 | D05964J | | 8 | | | D04528J | 26 | | | 277-299 |
| 302Y | 24 | PX | AM | 0-0 | 73-21-13 | D05964J | | 6 | | | D04528J | 25 | | | 050-099, 150-199, 275-276 |
| 302Y | 24 | PX | MB | 0-0 | 73-21-13 | D05964J | | 6 | | | D04528J | 25 | | | 277-299 |
| 302Z | | | AM | 0-0 | 73-21-13 | D05964J | | | FY | | D04528J | =CC | D | | 050-099, 157, 167-199 |
| 302Z | | | AM | 0-0 | 73-21-13 | D05964J | | | FB | | D04528J | =CC | D | | 150-156, 162-166 |
| 302Z | | | AM | 0-0 | 73-21-13 | D05964J | | | FE | | D04528J | =CC | D | | 275-276 |
| 302Z | | | MB | 0-0 | 73-21-13 | D05964J | | | FY | | D04528J | =CC | D | | 277-299 |
| 303B | 24 | PM | F | 33-3 | 27-51-31 | D08034J | | 10 | | | D08120P | 29 | | | ALL |
| 303R | 24 | PM | F | 0-0 | 27-51-31 | D08034J | | 11 | | | D08120P | 27 | | | ALL |
| 303Y | 24 | PM | F | 0-0 | 27-51-31 | D08034J | | 12 | | | D08120P | 28 | | | ALL |
| 304B | 22 | PC | AD | 88-7 | 27-58-21 | D04590J | | 17 | | | D08030P | 24 | | | 050-099 |
| 304B | 22 | PC | AD | 98-7 | 27-58-21 | D04590J | | 17 | | | D08030P | 24 | | | 150-199, 275-299 |
| 304R | 22 | PC | AD | 0-0 | 27-58-21 | D04590J | | 18 | | | D08030P | 25 | | | ALL |
| 304Y | 22 | PC | AD | 0-0 | 27-58-21 | D04590J | | 19 | | | D08030P | 26 | | | ALL |
| 306B | 24 | PM | AB | 50-4 | 27-81-31 | D04532J | | 3 | | | D05626J | 17 | | | 050-099 |
| 306B | 24 | PM | AB | 60-7 | 27-81-31 | D04532J | | 3 | | | D05626J | 17 | | | 150-199, 275-299 |
| 306R | 24 | PM | AB | 0-0 | 27-81-31 | D04532J | | 4 | | | D05626J | 18 | | | ALL |
| 306Y | 24 | PM | AB | 0-0 | 27-81-31 | D04532J | | 5 | | | D05626J | 19 | | | ALL |
| 309B | 20 | PC | MI | 110-2 | 27-58-11 | D04590J | | 2 | | | D05664P | 14 | | | 156-157, 166-199, 277-299 |
| 309R | 20 | PC | MI | 0-0 | 27-58-11 | D04590J | | 1 | | | D05664P | 13 | | | 156-157, 166-199, 277-299 |
| 309Y | 20 | PC | MI | 0-0 | 27-58-11 | D04590J | | 23 | | | D05664P | 52 | | | 156-157, 166-199, 277-299 |
| 313B | 24 | PM | H | 33-3 | 27-58-31 | D08034J | | 15 | | | D08120P | 34 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 19

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|----------|-------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | |
| 313R | 24 | PM | H | 0-0 | 27-58-31 | | D08034J | 16 | | | | D08120P | 32 | | | ALL |
| 313Y | 24 | PM | H | 0-0 | 27-58-31 | | D08034J | 17 | | | | D08120P | 33 | | | ALL |
| 402B | 22 | PT | L | 27-5 | 21-31-21 | | D08034J | 35 | | | | D04710P | 32 | | | 050-099, 150-199 |
| 402B | 22 | PT | QB | 27-5 | 21-31-21 | | D08034J | 35 | | | | D04710P | 32 | | | 275-299 |
| 402G | 22 | PT | L | 0-0 | 21-31-21 | | D08034J | 36 | | | | D04710P | 33 | | | 050-099, 150-199 |
| 402G | 22 | PT | QB | 0-0 | 21-31-21 | | D08034J | 36 | | | | D04710P | 33 | | | 275-299 |
| 402R | 22 | PT | L | 0-0 | 21-31-21 | | D08034J | 37 | | | | D04710P | 34 | | | 050-099, 150-199 |
| 402R | 22 | PT | QB | 0-0 | 21-31-21 | | D08034J | 37 | | | | D04710P | 34 | | | 275-299 |
| 402Y | 22 | PT | L | 0-0 | 21-31-21 | | D08034J | 38 | | | | D04710P | 35 | | | 050-099, 150-199 |
| 402Y | 22 | PT | QB | 0-0 | 21-31-21 | | D08034J | 38 | | | | D04710P | 35 | | | 275-299 |
| 402Z | | | L | 0-0 | 21-31-21 | | D08034J | 39 | | | | D04710P | 36 | | | 050-099, 150-199 |
| 402Z | | | QB | 0-0 | 21-31-21 | | D08034J | 39 | | | | D04710P | 36 | | | 275-299 |
| 403B | 22 | PD | AF | 78-0 | 27-51-41 | | D04610J | 3 | | | | D05626J | 22 | | | 050-099 |
| 403B | 22 | PD | AF | 88-0 | 27-51-41 | | D04610J | 3 | | | | D05626J | 22 | | | 150-199, 275-299 |
| 403G | 22 | PD | AF | 0-0 | 27-51-41 | | D04610J | 6 | | | | D05626J | 23 | | | ALL |
| 403R | 22 | PD | AF | 0-0 | 27-51-41 | | D04610J | 4 | | | | D05626J | 24 | | | ALL |
| 403Y | 22 | PD | AF | 0-0 | 27-51-41 | | D04610J | 5 | | | | D05626J | 25 | | | ALL |
| 407B | 24 | PN | C | 20-3 | 27-51-41 | | D05300P | 26 | | | | D05626J | 11 | | | ALL |
| 407G | 24 | PN | C | 0-0 | 27-51-41 | | D05300P | 29 | | | | D05626J | 12 | | | ALL |
| 407R | 24 | PN | C | 0-0 | 27-51-41 | | D05300P | 27 | | | | D05626J | 13 | | | ALL |
| 407Y | 24 | PN | C | 0-0 | 27-51-41 | | D05300P | 28 | | | | D05626J | 14 | | | ALL |
| 501 | 24 | PK | | 26-11 | 77-31-11 | | D05626J | 36 | | | | D04714P | 25 | | | ALL |
| 504 | 22 | PA | | 15-4 | 27-62-11 | | D01364 | 2 | | | | D08120P | 3 | | | ALL |
| 505 | 22 | PA | | 15-4 | 27-62-11 | | D01364 | 1 | | | | D08120P | 4 | | | ALL |
| 506 | 22 | PA | | 36-8 | 27-62-11 | | D05664P | 46 | | | | D08120P | 5 | | | ALL |
| 507 | 22 | PA | | 15-4 | 27-62-11 | | D01364 | 3 | | | | D08120P | 6 | | | ALL |
| 509 | 24 | PK | | 15-4 | 31-51-42 | | D01364 | 6 | | | | D08120P | 13 | | | ALL |
| 513 | 24 | PK | | 15-4 | 32-42-12 | | D01364 | 11 | | | | D08120P | 20 | | | ALL |
| 514 | 24 | PK | | 15-4 | 32-42-12 | | D01364 | 12 | | | | D08120P | 35 | | | ALL |
| 515 | 24 | PK | | 22-1 | 32-42-12 | | D04714P | 44 | | | | D08120P | 36 | | | ALL |
| 516 | 24 | PK | | 15-4 | 32-42-12 | | D01364 | 14 | | | | D08120P | 37 | | | ALL |
| 517 | 24 | PK | | 15-4 | 32-42-12 | | D01364 | 15 | | | | D08120P | 38 | | | ALL |
| 518 | 24 | PK | | 22-1 | 32-42-12 | | D04714P | 41 | | | | D08120P | 39 | | | ALL |
| 520 | 20 | PA | | 1-7 | 31-51-42 | | D01364 | 7 | | | | GD03814 | D.. | E | | 050-099, 275-299 |
| 520 | 20 | PA | | 1-7 | 31-51-42 | | D01364 | 7 | | | | GD03814 | D.. | E | *2 | 150-199 |
| 521 | 18 | PA | | 13-0 | 33-13-18 | | SP02288 | | 9 | | | D08120P | 10 | DK | | ALL |
| 522 | 24 | PK | | 22-1 | 32-42-12 | | D04714P | 42 | | | | D08120P | 40 | | | ALL |
| 523 | 22 | PA | | 30-10 | SPARE | | D05664P | | | CAP | Y | D04710P | | CAP | Y | 150-199 |
| 523 | 22 | PA | | 30-10 | SPARE | | D05664P | | | CAP | Y | D04710P | | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 20

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 524 | 22 | | PA | | 42-4 | SPARE | D05664P | CAP | Y | | D05300P | CAP | Y | | 150-199 |
| 524 | 22 | | PA | | 42-4 | SPARE | D05664P | CAP | Y | | D05300P | 38 | | | 275-299 |
| 525 | 24 | | PK | | 22-1 | 32-42-12 | D04714P | | | 43 | D08120P | 41 | | | ALL |
| 528 | 20 | | PA | | 5-0 | 33-13-18 | SP02272 | | | 9 | D01832 | 1 | | | 050-099, 150-155, 162-165, 275-276 |
| 529 | 20 | | PA | | 1-11 | 33-13-18 | GD04472 | A.. | | 2 | D01832 | 2 | | | 050-099, 150-155, 162-165, 275-276 |
| 531 | 20 | | PA | | 3-10 | 27-18-11 | D04590J | | | 20 | GD00792 | A.. | 2 | | 050-099 |
| 531 | 20 | | PA | | 4-3 | 27-18-11 | D04590J | | | 20 | GD00792 | A.. | 2 | | 150-199, 275-299 |
| 533 | 20 | | PA | | 3-10 | 27-18-11 | D04590J | | | 22 | GD00792 | A.. | 2 | | 050-099 |
| 533 | 20 | | PA | | 4-3 | 27-18-11 | D04590J | | | 22 | GD00792 | A.. | 2 | | 150-199, 275-299 |
| 537 | 22 | | PA | | 14-6 | 30-31-13 | D00568 | | | A | D04714P | 58 | | | ALL |
| 538 | 22 | | PA | | 29-1 | 30-31-13 | D00568 | | | B | D05664P | 41 | | | ALL |
| 541 | 20 | | UA | | 0-6 | 73-21-13 | D05964J | | | | GD03694 | S.. | E | | 150-152 |
| 542 | 20 | | UA | | 0-6 | 73-21-13 | D05964J | | | | GD03694 | S.. | E | | 150-152 |
| 546 | 24 | | PK | | 13-2 | 27-88-11 | D05626J | | | 6 | D05368J | 3 | | | ALL |
| 547 | 24 | | PK | | 13-2 | 27-88-11 | D05626J | | | 51 | D05368J | 4 | | | ALL |
| 553 | 24 | | PK | | 24-5 | 73-21-17 | D04710P | | | 30 | D08030P | 16 | | | ALL |
| 554 | 24 | | PK | | 15-5 | 21-31-11 | D05368J | | | 2 | SP02562 | | S | | ALL |
| 555 | 24 | | PK | | 30-0 | 21-31-11 | D01364 | | | 17 | SP02562 | | S | | ALL |
| 560 | 24 | | PV | WJ | 30-8 | 73-21-17 | D08030P | | | 7 | D05832P | 44 | | | 050-099, 275-299 |
| 560 | 24 | | PV | WJ | 30-8 | 73-21-17 | D05832P | | | 44 | D08030P | 7 | | | 150-199 |
| 560Z | | | | WJ | 0-0 | 73-21-17 | D08030P | | | 8 | D05832P | | | WK | 050-099 |
| 560Z | | | | WJ | 0-0 | 73-21-17 | D05832P | | | | D08030P | 8 | | | 150-199 |
| 560Z | | | | WJ | 0-0 | 73-21-17 | D08030P | | | 8 | D05832P | | | FJ | 275-299 |
| 561 | 24 | | PV | WK | 48-10 | 73-21-17 | D05832P | | | 45 | D04528J | 1 | | | 050-099 |
| 561 | 24 | | PV | WK | 59-2 | 73-21-17 | D05832P | | | 45 | D04528J | 1 | | | 150-199, 275-299 |
| 561Z | | | | WK | 0-0 | 73-21-17 | D05832P | | | | D04528J | =CC | D | | 050-099, 150-199 |
| 561Z | | | | WK | 0-0 | 73-21-17 | D05832P | | | | D04528J | =CC | L | | 275-276 |
| 561Z | | | | WK | 0-0 | 73-21-17 | D05832P | | | | D04528J | =CC | D | | 277-299 |
| 579 | 24 | | PK | | 14-9 | 24-11-11 | D05300P | | | 23 | D05368J | 17 | | | 050-099, 275-299 |
| 579 | 24 | | PK | | 14-9 | 24-11-11 | D05368J | | | 17 | D05300P | 23 | | | 150-199 |
| 580 | 24 | | PK | | 14-9 | 24-11-11 | D05300P | | | 30 | D05368J | 18 | | | 050-099 |
| 580 | 24 | | PK | | 14-9 | 24-11-11 | D05368J | | | 18 | D05300P | 30 | | | 150-199, 275-299 |
| 590 | 18 | | PA | | 46-5 | 78-34-11 | D05300P | | | CAP | D01364 | CAP | Y | | 050-099, 150-199 |
| 590 | 18 | | PA | | 46-5 | 78-34-11 | D01364 | | | CAP | D05300P | CAP | Y | | 275-299 |
| 592 | 24 | | PK | | 20-3 | 77-35-11 | D05300P | | | 46 | D05626J | 8 | | | 050-099, 150-199, 277-299 |
| 592 | 24 | | PK | | 20-3 | 77-35-11 | D05300P | | | 55 | D05626J | 8 | | | 275-276 |

WIRE LIST
D280T132

91-21-11
Section W0750
Page 21
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | |
| 595 | 18 | | PA | | 3-1 | 78-34-11 | D01364 | | 22 | DK | | GD00561 | D.. | 2 | | 050-099, 275-299 |
| 595 | 18 | | PA | | 1-7 | 78-34-11 | GD03814 | | D.. | E | | D01364 | | 22 | DK | 150-199 |
| 596 | 18 | | PA | | 37-1 | 78-34-11 | D04710P | | 2 | DL | | D05300P | | 13 | DK | ALL |
| 597 | 18 | | PA | | 37-1 | SPARE | D04710P | | 13 | DK | | D05300P | | 14 | DK | 050-099, 150-199 |
| 597 | 18 | | PA | | 37-1 | SPARE | D04710P | | 13 | DL | | D05300P | | 14 | DK | 275-299 |
| 599 | 18 | | PA | | 37-1 | SPARE | D04710P | | 10 | DK | | D05300P | | 16 | DK | 050-099 |
| 599 | 18 | | PA | | 37-1 | SPARE | D04710P | | 10 | DL | | D05300P | | 16 | DK | 150-199, 275-299 |
| 600 | 18 | | PA | | 37-1 | SPARE | D04710P | | 11 | DK | | D05300P | | 32 | DK | 050-099, 150-199 |
| 600 | 18 | | PA | | 37-1 | SPARE | D04710P | | 11 | DL | | D05300P | | 32 | DK | 275-299 |
| 601 | 18 | | PA | | 46-5 | 78-34-11 | D05300P | | CAP | Y | | D01364 | CAP | Y | | 050-099, 150-199 |
| 601 | 18 | | PA | | 46-5 | 78-34-11 | D01364 | | CAP | Y | | D05300P | CAP | Y | | 275-299 |
| 605 | 24 | | PK | | 49-3 | 24-11-11 | D06586J | | 4 | | | D05832P | | 19 | | 050-099 |
| 605 | 24 | | PK | | 59-6 | 24-11-11 | D06586J | | 4 | | | D05832P | | 19 | | 150-199, 275-299 |
| 606 | 24 | | PK | | 49-3 | 24-11-11 | D06586J | | 1 | | | D05832P | | 16 | | 050-099 |
| 606 | 24 | | PK | | 59-6 | 24-11-11 | D05832P | | 16 | | | D06586J | | 1 | | 150-199, 275-299 |
| 607 | 24 | | PK | | 49-3 | 24-11-11 | D06586J | | 3 | | | D05832P | | 18 | | 050-099 |
| 607 | 24 | | PK | | 59-6 | 24-11-11 | D06586J | | 3 | | | D05832P | | 18 | | 150-199, 275-299 |
| 608 | 24 | | PK | | 49-3 | 24-11-11 | D06586J | | 2 | | | D05832P | | 17 | | 050-099 |
| 608 | 24 | | PK | | 59-6 | 24-11-11 | D06586J | | 2 | | | D05832P | | 17 | | 150-199, 275-299 |
| 609 | 24 | | PV | AT | 29-8 | 73-21-14 | D05664P | | 31 | | | D08030P | | 9 | | 050-099 |
| 609 | 24 | | PV | BB | 29-8 | 73-21-14 | D05664P | | 31 | | | D08030P | | 9 | | 150-199 |
| 609 | 24 | | PV | YI | 29-8 | 73-21-14 | D05664P | | 31 | | | D08030P | | 9 | | 275-299 |
| 609Z | | | | AT | 0-0 | 73-21-14 | D05664P | | 32 | | | D08030P | | | | FI 050-099 |
| 609Z | | | | BB | 0-0 | 73-21-14 | D05664P | | 32 | | | D08030P | | | | FF 150-199 |
| 609Z | | | | YI | 0-0 | 73-21-14 | D05664P | | 32 | | | D08030P | | | | FI 275-299 |
| 636 | 24 | | PK | | 30-8 | 73-21-16 | D08030P | | 1 | | | D05832P | | 1 | | 050-099, 150-199 |
| 639 | 24 | | PK | | 30-10 | 73-21-18 | D08030P | | 50 | | | D05300P | | 59 | | 050-099 |
| 639 | 24 | | PK | | 30-10 | 73-21-18 | D05300P | | 59 | | | D08030P | | 50 | | 150-199, 275-299 |
| 641 | 16 | | PQ | YA | 48-10 | 73-21-11 | D04528J | | 6 | FM | | D05832P | | 55 | FM | 050-099 |
| 641 | 16 | | PA | | 59-2 | 73-21-11 | D04528J | | 6 | FM | | D05832P | | 55 | FM | 150-154, 275-276 |
| 641 | 18 | | PQ | YA | 59-2 | 73-21-11 | D04528J | | 6 | FM | | D05832P | | 55 | FM | 155-199 |
| 641 | 16 | | PQ | ZP | 59-2 | 73-21-11 | D04528J | | 6 | FM | | D05832P | | 55 | FM | 277-299 |
| 641Z | | | | YA | 0-0 | 73-21-11 | D04528J | | =CC | M | | D05832P | | 54 | FM | 050-099, 155-156, 162-166 |
| 641Z | | | | YA | 0-0 | 73-21-11 | D04528J | | =CC | D | | D05832P | | 54 | FM | 157, 167-199 |
| 641Z | | | | ZP | 0-0 | 73-21-11 | D04528J | | =CC | D | | D05832P | | 54 | FM | 277-299 |
| 642 | 22 | | PQ | ZQ | 35-0 | 28-22-31 | D04714P | | 53 | | | D05664P | | 53 | | ALL |
| 642Z | | | | ZQ | 0-0 | 28-22-31 | D04714P | | DED | | | D05664P | | DED | | ALL |
| 643 | 22 | | PQ | ZR | 35-0 | 28-22-31 | D04714P | | 54 | | | D05664P | | 54 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 22

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | |
| 643Z | | | ZR | 0-0 | 28-22-31 | D04714P | | DED | | | | | D05664P | DED | | | ALL |
| 644 | 22 | PQ | ZS | 35-0 | 28-22-31 | D04714P | | 55 | | | | | D05664P | 55 | | | ALL |
| 644Z | | | ZS | 0-0 | 28-22-31 | D04714P | | DED | | | | | D05664P | DED | | | ALL |
| 645 | 22 | PQ | ZT | 35-0 | 28-22-31 | D04714P | | 56 | | | | | D05664P | 29 | | | ALL |
| 645Z | | | ZT | 0-0 | 28-22-31 | D04714P | | DED | | | | | D05664P | DED | | | ALL |
| 646 | 20 | UA | | 4-7 | 78-34-11 | D05300P | | | | FU | | | GD00670 | S.. | 2 | | ALL |
| 650 | 20 | PA | | 5-0 | 78-34-11 | D08120P | | 24 | | | | | GD00591 | D.. | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 650 | 20 | PA | | 15-0 | 78-34-11 | D08120P | | 24 | | | | | GD00591 | D.. | 2 | | 157, 167-199, 277-299 |
| 655 | 24 | PK | | 31-2 | 78-36-11 | D04714P | | 18 | | | | | D05664P | CAP | Y | | ALL |
| 657 | 24 | PK | | 31-2 | 78-36-11 | D04714P | | 19 | | | | | D05664P | CAP | Y | | ALL |
| 658 | 24 | PK | | 42-3 | 78-36-11 | D05664P | | 4 | | | | | D05832P | 47 | | | ALL |
| 659 | 24 | PK | | 42-3 | 78-36-11 | D05664P | | 20 | | | | | D05832P | 48 | | | ALL |
| 660 | 24 | PK | | 42-4 | 78-36-11 | D05664P | | 21 | | | | | D05300P | 57 | | | 050-099, 275-299 |
| 660 | 24 | PK | | 42-4 | 78-36-11 | D05664P | | 21 | | | | | D05300P | 2 | | | 150-199 |
| 662 | 24 | PK | | 73-0 | 78-36-11 | D05664P | | 18 | | | | | D04486J | 39 | | | 050-099 |
| 662 | 24 | PK | | 82-9 | 78-36-11 | D05664P | | 18 | | | | | D04486J | 39 | | | 150-199, 275-299 |
| 663 | 18 | PQ | AX | 73-0 | 78-36-11 | D05664P | | | CAP | Y | | | D04486J | 33 | DK | | 050-099 |
| 663 | 18 | PQ | AX | 82-9 | 78-36-11 | D05664P | | | CAP | Y | | | D04486J | 33 | DK | | 150-199, 275-299 |
| 663Z | | | AX | 0-0 | 78-36-11 | D05664P | | | DED | | | | D04486J | =CC | D | | ALL |
| 664 | 18 | PQ | AY | 73-0 | 78-36-11 | D05664P | | | CAP | Y | | | D04486J | 34 | DK | | 050-099 |
| 664 | 18 | PQ | AY | 82-9 | 78-36-11 | D05664P | | | CAP | Y | | | D04486J | 34 | DK | | 150-199, 275-299 |
| 664Z | | | AY | 0-0 | 78-36-11 | D05664P | | | DED | | | | D04486J | =CC | D | | ALL |
| 665 | 20 | UA | | 11-4 | 78-36-11 | D05664P | | | | FP | | | GD00670 | S.. | 2 | | 275-299 |
| 666 | 20 | UA | | 5-0 | 78-34-11 | D01364 | | | | FM | | | GD00649 | S.. | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 666 | 20 | UA | | 15-0 | 78-34-11 | D01364 | | | | FM | | | GD00649 | S.. | 2 | | 157, 167-199, 277-299 |
| 668B | 18 | VG | YY | 73-0 | 78-36-11 | D04486J | | 35 | DK | | | | D05664P | CAP | Y | | 050-099 |
| 668B | 18 | VG | YY | 82-9 | 78-36-11 | D04486J | | 35 | DK | | | | D05664P | CAP | Y | | 150-199, 275-299 |
| 668R | 18 | VG | YY | 0-0 | 78-36-11 | D04486J | | 37 | DK | | | | D05664P | CAP | Y | | ALL |
| 668Z | | | YY | 0-0 | 78-36-11 | D04486J | | =CC | D | | | | D05664P | DED | | | ALL |
| 669B | 18 | VG | XX | 73-0 | 78-36-11 | D04486J | | 40 | DK | | | | D05664P | CAP | Y | | 050-099 |
| 669B | 18 | VG | XX | 82-9 | 78-36-11 | D04486J | | 40 | DK | | | | D05664P | CAP | Y | | 150-199, 275-299 |
| 669R | 18 | VG | XX | 0-0 | 78-36-11 | D04486J | | 41 | DK | | | | D05664P | CAP | Y | | ALL |
| 669Z | | | XX | 0-0 | 78-36-11 | D04486J | | =CC | D | | | | D05664P | DED | | | ALL |
| 680 | 20 | UA | | 10-0 | 78-34-11 | D20160 | | | | FT | | | GD00649 | S.. | 2 | | ALL |
| 681 | 18 | PQ | D1 | 47-0 | 78-34-11 | D20160 | | 8 | DK | | | | D05664P | 12 | DK | | ALL |
| 681Z | | | D1 | 0-0 | 78-34-11 | D20160 | | | | FT | | | D05664P | 11 | | | ALL |
| 682 | 18 | PQ | D2 | 55-0 | 78-34-11 | D20160 | | 5 | DK | | | | D05832P | 50 | DK | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 23

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | |
| 682Z | | | | D2 | 0-0 | 78-34-11 | D20160 | | | | FT | D05832P | | | FR | ALL |
| 683 | 20 | PA | | | 42-3 | 78-34-11 | D05664P | | 1 | | | D05832P | | 6 | | ALL |
| 684 | 20 | UA | | | 4-5 | 78-34-11 | D05832P | | | | FR | GD00670 | | S.. 2 | | ALL |
| 685 | 24 | PK | | | 14-8 | 78-34-11 | D05832P | | 38 | | | D05368J | | 24 | | ALL |
| 703 | 20 | PA | | | 26-2 | 30-81-11 | D12138 | | 1 | | | D04714P | | 20 | | 050-099, 150-199 |
| 704 | 20 | PA | | | 43-5 | 30-81-11 | D12138 | | 2 | | | D05664P | | 26 | | 050-099, 150-199 |
| 705 | 20 | PA | | | 9-8 | 30-81-11 | D12138 | | 3 | | | GD02464 | | D.. 2 | | 050-099, 150-199 |
| 706 | 20 | PA | | | 43-5 | 30-81-11 | D12138 | | 4 | | | D05664P | | 38 | | 050-099, 150-199 |
| 707 | 20 | PA | | | 26-2 | 30-81-11 | D12138 | | 5 | | | D04714P | | 26 | | 050-099, 150-199 |
| 708 | 20 | PA | | | 43-5 | 30-81-11 | D12138 | | 6 | | | D05664P | | 24 | | 050-099, 150-199 |
| 709 | 20 | PA | | | 9-8 | 30-81-11 | D12138 | | 7 | | | GD02464 | | A.. 2 | | 050-099, 150-199 |
| 70D | 20 | PA | | | 31-2 | 29-11-14 | D04714P | | 46 | | | D05664P | | 51 | | ALL |
| 70E | 20 | PA | | | 31-2 | 29-11-14 | D04714P | | 47 | | | D05664P | | 50 | | ALL |
| 70F | 20 | PA | | | 31-2 | 29-11-14 | D04714P | | 48 | | | D05664P | | 49 | | ALL |
| 710 | 20 | PA | | | 9-8 | 30-81-11 | D12138 | | 8 | | | GD02464 | | S.. 2 | | 050-099, 150-199 |
| 711 | 20 | PA | | | 43-5 | 30-81-11 | D12138 | | 12 | | | D05664P | | 40 | | 050-099, 150-199 |
| 712 | 20 | PA | | | 31-2 | 30-81-11 | D04714P | | 32 | | | D05664P | | 43 | | 155, 162-165 |
| 712 | 20 | PA | | | 31-2 | 30-81-11 | D04714P | | 32 | | | D05664P | | CAP Y | | 156-157, 166-199 |
| 801 | 24 | PK | | | 30-0 | 74-31-11 | D04710P | | 6 | | | D05368J | | 31 | | ALL |
| 802 | 22 | PA | | | 61-6 | 36-22-11 | D08030P | | 44 | | | D04486J | | 32 | | 050-099 |
| 802 | 22 | PA | | | 71-2 | 36-22-11 | D08030P | | 44 | | | D04486J | | 32 | | 150-199, 275-299 |
| 803 | 22 | PA | | | 24-5 | 36-22-11 | D08030P | | 41 | | | D04710P | | 5 | | ALL |
| 805 | 22 | PA | | | 26-6 | 27-88-11 | D05626J | | 1 | | | D04710P | | 19 | | ALL |
| 806 | 20 | PA | | | 1-7 | 24-22-11 | D01364 | | 5 | | | GD03814 | | D.. E | | 050-099, 275-299 |
| 806 | 20 | PA | | | 1-7 | 24-22-11 | D01364 | | 5 | | | GD03814 | | D.. E | *2 | 150-199 |
| 807 | 24 | PK | | | 30-0 | 24-22-11 | D01364 | | 4 | | | SP02494 | | 9 | | ALL |
| 808 | 24 | PK | | | 22-5 | 24-22-11 | D05832P | | 8 | | | SP02494 | | 9 | | ALL |
| 809 | 24 | PK | | | 46-5 | SPARE | D05300P | | 57 | | | D01364 | | 19 | | 150-154 |
| 809 | 24 | PK | | | 46-5 | 73-21-11 | D05300P | | 57 | | | D01364 | | 19 | | 155-199 |
| 810 | 24 | PK | | | 40-1 | SPARE | D05664P | | 37 | | | D01364 | | 20 | | 150-154 |
| 810 | 24 | PK | | | 40-1 | 73-21-11 | D05664P | | 37 | | | D01364 | | 20 | | 155-199 |
| 811 | 24 | PK | | | 30-10 | SPARE | D05300P | | | CAP Y | | D08030P | | 3 | | 150-199 |
| 813 | 24 | PV | CV | | 48-10 | 73-21-11 | D05832P | | 36 | | | D04528J | | 8 | | 050-099 |
| 813 | 24 | PV | BG | | 59-2 | 73-21-11 | D05832P | | 36 | | | D04528J | | 8 | | 150-199 |
| 813 | 24 | PV | R3 | | 59-2 | 73-21-11 | D05832P | | 36 | | | D04528J | | 8 | | 275-299 |
| 813Z | | | CV | | 0-0 | 73-21-11 | D05832P | | 37 | | | D04528J | | =CC D | | 050-099 |
| 813Z | | | BG | | 0-0 | 73-21-11 | D05832P | | 37 | | | D04528J | | =CC M | | 150-156, 162-166 |
| 813Z | | | BG | | 0-0 | 73-21-11 | D05832P | | 37 | | | D04528J | | =CC D | | 157, 167-199 |
| 813Z | | | R3 | | 0-0 | 73-21-11 | D05832P | | 37 | | | D04528J | | =CC L | | 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 24

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|---------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 813Z | | | | R3 | 0-0 | 73-21-11 | D05832P | | 37 | | D04528J | =CC | D | | 277-299 |
| 815 | 24 | PK | | | 21-2 | 27-51-31 | D08030P | | 11 | | D08034J | 4 | | | ALL |
| 816 | 24 | PK | | | 21-2 | 27-58-31 | D08030P | | 42 | | D08034J | 18 | | | ALL |
| 817 | 22 | PA | | | 25-0 | 73-21-19 | D08030P | | 43 | | D08016P | 5 | | | 050-099, 275-299 |
| 817 | 22 | PA | | | 25-0 | 73-21-19 | D08016P | | 5 | | D08030P | 43 | | | 150-199 |
| A-A | | | | | 0-0 | 27-18-11 | SP02638 | | | 9 | M01150 | B | | | 050-099, 150-154, 162-165, 275-276 |
| A-B | | | | | 0-0 | 27-18-11 | SP02642 | | | 9 | M01151 | B | | | 050-099, 150-154, 162-165, 275-276 |
| FR2 | | | | | 0-0 | 73-21-13 | D05964J | | | | FX | GD03694 | S.. | E | 050-099, 157, 167-199, 277-299 |
| FR3 | | | | | 0-0 | 73-21-13 | D05964J | | | | FY | GD03694 | S.. | E | 050-099, 157, 167-199, 277-299 |
| FRA | | | | | 0-0 | 73-21-13 | D05964J | | 10 | | D05964J | | | FA | 150-156, 162-166 |
| FRA | | | | | 0-0 | 73-21-11 | D08030P | | 48 | | D08030P | | | FA | 275-299 |
| FRB | | | | | 0-0 | 73-21-13 | D05964J | | 1 | | D05964J | | | FB | 150-156, 162-166 |
| FRB | | | | | 0-0 | 31-35-14 | D04791J | | 15 | | D04791J | | | FB | 277 |
| FRC | | | | | 0-0 | 73-21-11 | D04710P | | | | FC | D04710P | 21 | | 050-099, 150-199 |
| FRC | | | | | 0-0 | 73-21-11 | D04710P | | 21 | | D04710P | | | FC | 275-299 |
| FRD | | | | | 0-0 | 73-21-11 | D08030P | | 48 | | D08030P | | | FD | 050-099 |
| FRD | | | | | 0-0 | 73-21-11 | D08030P | | | | FD | D08030P | 48 | | 150-199 |
| FRE | | | | | 0-0 | 73-21-11 | D05832P | | | | FE | D05832P | 29 | | 050-099, 150-199 |
| FRE | | | | | 0-0 | 73-21-11 | D05832P | | 29 | | D05832P | | | FE | 277-299 |
| FRF | | | | | 0-0 | 73-21-17 | D08030P | | | | FF | D08030P | 13 | | 150-199 |
| FRG | | | | | 0-0 | 73-21-14 | D08034J | | | | FG | D08034J | 48 | | 275-299 |
| FRI | | | | | 0-0 | 73-21-17 | D08030P | | | | FI | D08030P | 13 | | 050-099 |
| FRI | | | | | 0-0 | 73-21-17 | D08030P | | 13 | | D08030P | | | FI | 275-299 |
| FRJ | | | | | 0-0 | 73-21-17 | D05832P | | 46 | | D05832P | | | FJ | 275-299 |
| FRL | | | | | 0-0 | 73-21-14 | D08034J | | | | FL | D08034J | 48 | | 050-099, 150-199 |
| FRM | | | | | 0-0 | 73-21-13 | D05964J | | | | FA | GD03694 | S.. | E | 153-156, 162-166 |
| FRN | | | | | 0-0 | 73-21-13 | D05964J | | | | FB | GD03694 | S.. | E | 153-156, 162-166 |
| FRO | | | | | 0-0 | 78-34-21 | D04710P | | | | FO | D04710P | 46 | | ALL |
| FRQ | | | | | 0-0 | 78-34-11 | D20160 | | | | FT | D20160 | 7 | | ALL |
| FRR | | | | | 0-0 | 78-34-11 | D05832P | | | | FR | D05832P | 14 | | ALL |
| FRS | | | | | 0-0 | 73-21-13 | D05964J | | | | FE | GD03694 | S.. | E | 275-276 |
| FRT | | | | | 0-0 | 78-34-11 | D20160 | | | | FT | D20160 | 4 | | ALL |
| FRU | | | | | 0-0 | 78-34-11 | D05300P | | | | FU | D05300P | 56 | | ALL |
| FRV | | | | | 0-0 | 78-34-21 | D05832P | | | | FV | D05832P | 31 | | ALL |
| FRW | | | | | 0-0 | 31-35-14 | D04528J | | | | FW | D04528J | =CC | | 277 |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 25

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|---------|-------------|---|----|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0756 | 286T0756 | | | P61 TO L WING RS - L2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | | |
| FRX | | | | 0-0 | 73-21-13 | D05964J | | 10 | | | | | D05964J | | | | FX | 050-099, 157, 167-199, 277-299 |
| FRY | | | | 0-0 | 73-21-13 | D05964J | | 1 | | | | | D05964J | | | | FY | 050-099, 157, 167-199, 277-299 |
| FRZ | | | | 0-0 | 73-21-17 | D05832P | | | | | | | WK | D05832P | 46 | | | 050-099 |
| W0758 | 286T0758 | | | L WING RS - L2B - EEC CH. B | | | | | | | | | | | | | | |
| 001 | 20 | | PA | 49-0 | 30-34-11 | D06582P | | 8 | | | | | D06578J | 14 | | | | 050-099 |
| 001 | 20 | | PA | 59-0 | 30-34-11 | D06582P | | 8 | | | | | D06578J | 14 | | | | 150-199, 275-299 |
| 002 | 20 | | PQ AB | 49-0 | 73-21-14 | D06582P | | 11 | | | | | D06578J | 2 | | | | 050-099 |
| 002 | 20 | | PQ AB | 59-0 | 73-21-14 | D06582P | | 11 | | | | | D06578J | 2 | | | | 150-199, 275-299 |
| 002Z | | | AB | 0-0 | 73-21-14 | D06582P | | | | | | | FD | D06578J | = CC | M | | ALL |
| 004 | 24 | | PV AG | 49-0 | 73-21-11 | D06582P | | 17 | | | | | D06578J | 8 | | | | 050-099 |
| 004 | 24 | | PV AG | 59-0 | 73-21-11 | D06582P | | 17 | | | | | D06578J | 8 | | | | 150-199, 275-299 |
| 004Z | | | AG | 0-0 | 73-21-11 | D06582P | | | | | | | FC | D06578J | = CC | M | | ALL |
| 009 | 24 | | PV AH | 49-0 | 73-21-11 | D06582P | | 18 | | | | | D06578J | 9 | | | | 050-099 |
| 009 | 24 | | PV AH | 59-0 | 73-21-11 | D06582P | | 18 | | | | | D06578J | 9 | | | | 150-199, 275-299 |
| 009Z | | | AH | 0-0 | 73-21-11 | D06582P | | | | | | | FC | D06578J | = CC | M | | ALL |
| 013 | 16 | | PQ AC | 49-0 | 73-21-20 | D06582P | | 2 | FL | | | | D06578J | 13 | FM | | | 050-099 |
| 013 | 16 | | PQ AC | 59-0 | 73-21-20 | D06582P | | 2 | FL | | | | D06578J | 13 | FM | | | 150-199, 275-299 |
| 013Z | | | AC | 0-0 | 73-21-20 | D06582P | | | | | | | FD | D06578J | = CC | M | | ALL |
| 142 | 20 | | UA | 2-0 | 73-21-13 | D04734J | | | | | | | FY | GD05408 | S.. | E | | 050-099, 150-156, 162-166, 275-276 |
| 143 | 20 | | UA | 2-0 | 73-21-13 | D04734J | | | | | | | FX | GD05408 | S.. | E | | 050-099, 150-156, 162-166, 275-276 |
| 200B | 24 | | PW HY | 49-0 | 31-35-14 | D06578J | | 6 | | | | | D06582P | 26 | | | | 050-099 |
| 200B | 24 | | PW HY | 59-0 | 31-35-14 | D06582P | | 26 | | | | | D06578J | 6 | | | | 150-154, 275-276, 278-299 |
| 200B | 24 | | PW HY | 59-0 | 31-35-14 | D06578J | | 6 | | | | | D06582P | 26 | | | | 155-199 |
| 200R | 24 | | PW HY | 0-0 | 31-35-14 | D06578J | | 5 | | | | | D06582P | 25 | | | | 050-099, 155-199 |
| 200R | 24 | | PW HY | 0-0 | 31-35-14 | D06582P | | 25 | | | | | D06578J | 5 | | | | 150-154, 275-276, 278-299 |
| 200Z | | | HY | 0-0 | 31-35-14 | D06578J | | | | | | | = CC | D06582P | 27 | M | | 050-099, 155-199 |
| 200Z | | | HY | 0-0 | 31-35-14 | D06582P | | 27 | | | | | D06578J | = CC | D | | | 150-154 |
| 200Z | | | HY | 0-0 | 31-35-14 | D06582P | | 27 | | | | | D06578J | = CC | M | | | 275-276, 278-299 |
| 201B | 22 | | PR AL | 49-0 | 73-21-14 | D06582P | | 3 | | | | | D06578J | 21 | | | | 050-099 |
| 201B | 22 | | PR AL | 59-0 | 73-21-14 | D06582P | | 3 | | | | | D06578J | 21 | | | | 150-199, 275-299 |
| 201R | 22 | | PR AL | 0-0 | 73-21-14 | D06582P | | 4 | | | | | D06578J | 22 | | | | ALL |
| 201Z | | | AL | 0-0 | 73-21-14 | D06582P | | | | | | | FI | D06578J | = CC | M | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0750

Page 26

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0758 | 286T0758 | | | L WING RS - L2B - EEC CH. B (continued) | | | | | | | | | | | | |
| 202B | 24 | PW | IB | | 49-0 | 73-21-14 | D06582P | | 5 | | | D06578J | | 17 | | 050-099 |
| 202B | 24 | PW | IB | | 59-0 | 73-21-14 | D06582P | | 5 | | | D06578J | | 17 | | 150-199, 275-299 |
| 202R | 24 | PW | IB | | 0-0 | 73-21-14 | D06582P | | 6 | | | D06578J | | 18 | | ALL |
| 202Z | | | IB | | 0-0 | 73-21-14 | D06582P | | | | FI | D06578J | = CC | M | | ALL |
| 203B | 24 | PW | IC | | 49-0 | 73-21-14 | D06582P | | 10 | | | D06578J | | 12 | | 050-099 |
| 203B | 24 | PW | IC | | 59-0 | 73-21-14 | D06582P | | 10 | | | D06578J | | 12 | | 150-199, 275-299 |
| 203R | 24 | PW | IC | | 0-0 | 73-21-14 | D06582P | | 7 | | | D06578J | | 11 | | ALL |
| 203Z | | | IC | | 0-0 | 73-21-14 | D06582P | | | | FD | D06578J | = CC | M | | ALL |
| 205B | 24 | PW | IE | | 63-0 | 73-21-13 | D04734J | | 11 | | | D06578J | | 15 | | 050-099 |
| 205B | 24 | PW | IE | | 73-0 | 73-21-13 | D04734J | | 11 | | | D06578J | | 15 | | 150-199, 275-299 |
| 205R | 24 | PW | IE | | 0-0 | 73-21-13 | D04734J | | 12 | | | D06578J | | 16 | | ALL |
| 205Z | | | IE | | 0-0 | 73-21-13 | D04734J | | | | FX | D06578J | = CC | M | | ALL |
| 211B | 20 | PR | AU | | 49-0 | 73-21-17 | D06582P | | 19 | | | D06578J | | 10 | | 050-099 |
| 211B | 20 | PR | AU | | 59-0 | 73-21-17 | D06582P | | 19 | | | D06578J | | 10 | | 150-199, 275-299 |
| 211R | 20 | PR | AU | | 0-0 | 73-21-12 | D06582P | | 14 | | | D06578J | | 1 | | ALL |
| 211Z | | | AU | | 0-0 | 73-21-12 | D06582P | | 15 | | | D06578J | = CC | M | | ALL |
| 230B | 24 | PW | JE | | 49-0 | 77-12-11 | D06582P | | 23 | | | D06578J | | 3 | | 050-099 |
| 230B | 24 | PW | JE | | 59-0 | 77-12-11 | D06582P | | 23 | | | D06578J | | 3 | | 150-199, 275-299 |
| 230R | 24 | PW | JE | | 0-0 | 77-12-11 | D06582P | | 22 | | | D06578J | | 4 | | ALL |
| 230Z | | | JE | | 0-0 | 77-12-11 | D06582P | | 24 | | | D06578J | = CC | M | | ALL |
| 302B | 24 | PX | MB | | 63-0 | 73-21-13 | D04734J | | 7 | | | D06578J | | 27 | | 050-099 |
| 302B | 24 | PX | MB | | 73-0 | 73-21-13 | D04734J | | 7 | | | D06578J | | 27 | | 150-199, 275-299 |
| 302R | 24 | PX | MB | | 0-0 | 73-21-13 | D04734J | | 8 | | | D06578J | | 26 | | ALL |
| 302Y | 24 | PX | MB | | 0-0 | 73-21-13 | D04734J | | 6 | | | D06578J | | 25 | | ALL |
| 302Z | | | MB | | 0-0 | 73-21-13 | D04734J | | | | FY | D06578J | = CC | M | | ALL |
| FR2 | | | | | 0-0 | 73-21-13 | D04734J | | | | FX | GD05408 | S.. | E | | 157, 167-199, 277-299 |
| FR3 | | | | | 0-0 | 73-21-13 | D04734J | | | | FY | GD05408 | S.. | E | | 157, 167-199, 277-299 |
| FRC | | | | | 0-0 | 73-21-11 | D06582P | | | | FC | D06582P | | 16 | | ALL |
| FRD | | | | | 0-0 | 73-21-14 | D06582P | | | | FD | D06582P | | 13 | | ALL |
| FRI | | | | | 0-0 | 73-21-14 | D06582P | | | | FI | D06582P | | 9 | | ALL |
| FRX | | | | | 0-0 | 73-21-13 | D04734J | | | | FX | D04734J | | 10 | | ALL |
| FRY | | | | | 0-0 | 73-21-13 | D04734J | | | | FY | D04734J | | 1 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0750
Page 27 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|---------|-------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0764 | 286T0764 | | | P61 TO R WING FRONT SPAR-R2B-ENG INSTR/FLT CONT | | | | | | | | | | | | |
| 002 | 24 | | PK | 61-11 | 73-34-11 | D06238P | A11 | \$D | | D04622J | | 2 | | | 050-099 | |
| 002 | 24 | | PK | 71-9 | 73-34-11 | D04622J | | 2 | | D06238P | | A11 | | | 150-199 | |
| 002 | 24 | | PK | 71-9 | 73-34-11 | D06238P | | A11 | | D04622J | | 2 | | | 275-299 | |
| 003 | 18 | | PA | 57-0 | SPARE | D04754P | 28 | DL | | D04622J | | 18 | DK | | 050-099 | |
| 003 | 18 | | PA | 66-9 | SPARE | D04754P | 28 | DL | | D04622J | | 18 | DK | | 150-199, 275-299 | |
| 006 | 22 | | PA | 57-0 | SPARE | D04622J | | 6 | | D04754P | | 13 | | | 050-099 | |
| 007 | 24 | | PK | 57-0 | SPARE | D04622J | | 7 | | D04754P | | 14 | | | 050-099 | |
| 008 | 24 | | PK | 57-0 | SPARE | D04622J | | 8 | | D04754P | | 15 | | | 050-099 | |
| 009 | 22 | | PA | 57-0 | 29-11-21 | D04622J | | 9 | | D04754P | | 16 | | | 050-099 | |
| 009 | 22 | | PA | 66-9 | 29-11-21 | D04622J | | 9 | | D04754P | | 16 | | | 150-199, 275-299 | |
| 010 | 20 | | PA | 60-3 | SPARE | D04622J | | 40 | | D05328P | | CAP | Y | | 150-199, 275-276, 280-299 | |
| 010 | 20 | | PA | 60-3 | SPARE | D04622J | | 40 | | D05328P | | 17 | | | 277-278 | |
| 012 | 22 | | PA | 49-11 | 74-31-21 | D04622J | | 12 | | D05328P | | 10 | | | 050-099 | |
| 012 | 22 | | PA | 60-3 | 74-31-21 | D04622J | | 12 | | D05328P | | 10 | | | 150-199, 275-299 | |
| 021 | 22 | | PA | 15-5 | 74-31-21 | D05328P | | 3 | | D04754P | | 3 | | | ALL | |
| 027 | 20 | | PA | 15-5 | SPARE | D04754P | | 31 | | D05328P | | 12 | | | ALL | |
| 028 | 20 | | PA | 57-0 | SPARE | D04754P | | CAP | Y | D04622J | | 21 | | | 050-099 | |
| 028 | 20 | | PA | 66-9 | SPARE | D04754P | | CAP | Y | D04622J | | 21 | | | 150-199, 275-299 | |
| 029 | 22 | | PA | 15-5 | 74-31-21 | D05328P | | 1 | | D04754P | | 1 | | | ALL | |
| 030 | 22 | | PA | 15-5 | 74-31-21 | D05328P | | 2 | | D04754P | | 2 | | | ALL | |
| 031 | 18 | | PA | 14-2 | 27-81-21 | D06178J | | 14 | DK | D04754P | | 4 | DL | | ALL | |
| 032 | 18 | | PA | 19-0 | 27-81-21 | D06178J | | 15 | DK | D05328P | | 4 | DK | | ALL | |
| 033 | 18 | | PA | 19-0 | 27-81-21 | D06178J | | 16 | DK | D05328P | | 5 | DK | | ALL | |
| 034 | 20 | | PA | 19-0 | 27-81-21 | D06178J | | 17 | | D05328P | | 6 | DK | | 050-099 | |
| 034 | 20 | | PA | 19-0 | 27-81-21 | D06178J | | 17 | | D05328P | | 6 | | | 150-199, 275-299 | |
| 036 | 22 | | PA | 14-2 | 32-31-11 | D06178J | | 1 | | D04754P | | 5 | | | ALL | |
| 037 | 22 | | PA | 14-2 | 32-31-11 | D06178J | | 2 | | D04754P | | 6 | | | ALL | |
| 038 | 24 | | PK | 14-2 | 32-41-11 | D06178J | | 3 | | D04754P | | 8 | | | ALL | |
| 039 | 24 | | PK | 19-0 | 32-41-11 | D06178J | | 4 | | D05328P | | 39 | | | ALL | |
| 040 | 24 | | PK | 19-0 | 32-41-11 | D06178J | | 5 | | D05328P | | 40 | | | ALL | |
| 041 | 22 | | PA | 42-5 | 31-41-11 | D06256P | | 1 | | D04754P | | 11 | | | ALL | |
| 042 | 22 | | PA | 42-5 | 31-41-17 | D06256P | | 7 | | D04754P | | 10 | | | ALL | |
| 044 | 24 | | PK | 15-5 | 49-72-11 | D05328P | | 41 | | D04754P | | 21 | | | 050-099, 162-199, 275-299 | |
| 046 | 20 | | PA | 1-5 | 77-35-11 | D08610 | | 1 | | GD00691 | | D.. | 2 | | ALL | |
| 047 | 20 | | UA | 1-5 | 28-41-11 | D08610 | | | | GD00691 | | S.. | 2 | | ALL | |
| 047B | 24 | | PW | A | 13-5 | 28-41-11 | | 19 | | D08610 | | 11 | | | 050-099, 150-199 | |
| 047B | 24 | | PW | BV | 13-5 | 28-41-11 | | 11 | | D05328P | | 19 | | | 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0764 | 286T0764 | | | P61 TO R WING FRONT SPAR-R2B-ENG INSTR/FLT CONT (continued) | | | | | | | | | | | |
| 047R | 24 | PW | A | | 0-0 | 28-41-11 | D05328P | 26 | | | D08610 | 12 | | | 050-099, 150-199 |
| 047R | 24 | PW | BV | | 0-0 | 28-41-11 | D08610 | 12 | | | D05328P | 26 | | | 275-299 |
| 047Z | | | A | | 0-0 | 28-41-11 | D05328P | 15 | | | D08610 | | | BV | 050-099, 150-199 |
| 047Z | | | BV | | 0-0 | 28-41-11 | D08610 | | | BV | D05328P | 15 | | | 275-299 |
| 049 | 20 | PA | | | 57-0 | SPARE | D04622J | 41 | | | D04754P | 40 | | | 050-099 |
| 049 | 20 | PA | | | 66-9 | SPARE | D04622J | 41 | | | D04754P | 40 | | | 150-199, 275-299 |
| 050 | 20 | PA | | | 57-0 | SPARE | D04622J | 22 | | | D04754P | 41 | | | 050-099 |
| 050 | 20 | PA | | | 66-9 | SPARE | D04622J | 22 | | | D04754P | 41 | | | 150-199, 275-299 |
| 053 | 24 | PK | | | 42-7 | 79-32-11 | D04754P | 7 | | | D06238P | A10 | \$D | | ALL |
| 064 | 24 | PK | | | 36-1 | SPARE | D06238P | A08 | \$D | | D05328P | CAP | Y | | 150-199 |
| 067 | 24 | PK | | | 0-7 | SPARE | D06238P | A14 | \$D | | D06238P | CAP | Y | | 050-099 |
| 068 | 24 | PK | | | 0-7 | SPARE | D06238P | A15 | \$D | | D06238P | CAP | Y | | 050-099 |
| 069 | 24 | PK | | | 71-9 | SPARE | D06238P | A09 | \$D | | D04622J | CAP | Y | | 150-199 |
| 070 | 24 | PK | | | 0-7 | SPARE | D06238P | A17 | \$D | | D06238P | CAP | Y | | 050-099, 275-299 |
| 070 | 24 | PK | | | 36-1 | SPARE | D06238P | A01 | \$D | | D05328P | CAP | Y | | 150-199 |
| 071 | 24 | PK | | | 0-7 | SPARE | D06238P | A18 | \$D | | D06238P | CAP | Y | | 050-099, 275-299 |
| 071 | 24 | PK | | | 42-7 | SPARE | D06238P | A18 | \$D | | D04754P | CAP | Y | | 150-199 |
| 072 | 24 | PK | | | 0-7 | SPARE | D06238P | A19 | \$D | | D06238P | CAP | Y | | 050-099, 275-299 |
| 072 | 24 | PK | | | 22-2 | SPARE | D06238P | A19 | \$D | | D05428J | CAP | Y | | 150-199 |
| 076 | 24 | PK | | | 35-10 | 31-41-13 | D05328P | 8 | | | D06256P | 8 | | | ALL |
| 077 | 24 | PK | | | 35-10 | 31-41-13 | D05328P | 9 | | | D06256P | 9 | | | ALL |
| 078 | 24 | PK | | | 71-9 | SPARE | D06238P | A15 | \$D | | D04622J | 6 | | | 150-199 |
| 079 | 24 | PK | | | 66-9 | SPARE | D04622J | 7 | | | D04754P | 14 | | | 150-199 |
| 080 | 24 | PK | | | 71-9 | SPARE | D06238P | A14 | \$D | | D04622J | 8 | | | 150-199 |
| 091 | 16 | PQ | DP | | 11-0 | 73-21-11 | SP04056 | 9 | | | D05328P | 16 | FM | | 050-099 |
| 091 | 16 | PQ | DP | | 10-1 | 73-21-11 | SP04056 | S | | | D05328P | 16 | FM | | 150-154 |
| 091 | 16 | PQ | DP | | 10-1 | 73-21-11 | SP04056 | 9 | | | D05328P | 16 | FM | | 155-199, 277-299 |
| 091 | 16 | PQ | DP | | 18-0 | 73-21-11 | SP04056 | S | | | D05328P | 16 | FM | | 275-276 |
| 091Z | | | DP | | 0-0 | 73-21-11 | SP04056 | REF | V | | D05328P | 11 | | | ALL |
| 093 | 20 | PA | | | 15-5 | 73-21-11 | D04754P | 9 | | | D05328P | 7 | | | ALL |
| 094 | 16 | PA | | | 15-5 | 73-21-11 | D04754P | 12 | EN | | D05328P | 13 | EO | | 050-099, 155-199 |
| 094 | 16 | PA | | | 15-5 | 73-21-11 | D04754P | 12 | FL | | D05328P | 13 | FM | | 150-154, 275-299 |
| 133 | 18 | PQ | FH | | 57-0 | 78-34-21 | D04754P | 29 | DL | | D04622J | 49 | DK | | 050-099 |
| 133 | 18 | PQ | FH | | 66-9 | 78-34-21 | D04754P | 29 | DL | | D04622J | 49 | DK | | 150-156, 162-199, 275-278 |
| 133 | 18 | PQ | FH | | 66-9 | 78-34-21 | D04754P | 29 | DL | | D04622J | 47 | DK | | 157, 280-299 |
| 133Z | | | FH | | 0-0 | 78-34-21 | D04754P | 30 | | | D04622J | =CC | D | | ALL |
| 201B | 24 | PL | IA | | 46-5 | 78-34-21 | D05428J | 1 | | | D04622J | 23 | | | 050-099 |
| 201B | 24 | PL | B | | 56-9 | 78-34-21 | D04622J | 23 | | | D05428J | 1 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|--|----------|---------|---------|-------|------|------|---------|-------|-------------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0764 | 286T0764 | | | P61 TO R WING FRONT SPAR-R2B-ENG INSTR/FLT CONT (continued) | | | | | | | | | | | |
| 201R | 24 | PL | IA | 0-0 | 78-34-21 | D05428J | | 2 | | | D04622J | 24 | | | 050-099 |
| 201R | 24 | PL | B | 0-0 | 78-34-21 | D04622J | | 24 | | | D05428J | 2 | | | 150-199, 275-299 |
| 202B | 24 | PL | IB | 46-5 | 78-34-21 | D05428J | | 3 | | | D04622J | 25 | | | 050-099 |
| 202B | 24 | PL | C | 56-9 | 78-34-21 | D04622J | | 25 | | | D05428J | 3 | | | 150-199, 275-299 |
| 202R | 24 | PL | IB | 0-0 | 78-34-21 | D05428J | | 4 | | | D04622J | 26 | | | 050-099 |
| 202R | 24 | PL | C | 0-0 | 78-34-21 | D04622J | | 26 | | | D05428J | 4 | | | 150-199, 275-299 |
| 207B | 22 | PB | H | 57-0 | SPARE | D04622J | | 32 | | | D04754P | 32 | | | 050-099 |
| 207B | 22 | PB | H | 66-9 | SPARE | D04622J | | 32 | | | D04754P | 32 | | | 150-199, 275-299 |
| 207R | 22 | PB | H | 0-0 | SPARE | D04622J | | 33 | | | D04754P | 33 | | | ALL |
| 210B | 24 | PW | B | 19-0 | 73-21-14 | D06178J | | 10 | | | D05328P | 20 | | | 050-099 |
| 210B | 24 | PW | M | 19-0 | 73-21-14 | D06178J | | 10 | | | D05328P | 20 | | | 150-199 |
| 210B | 24 | PW | IJ | 19-0 | 73-21-14 | D06178J | | 10 | | | D05328P | 20 | | | 275-299 |
| 210R | 24 | PW | B | 0-0 | 73-21-14 | D06178J | | 9 | | | D05328P | 21 | | | 050-099 |
| 210R | 24 | PW | M | 0-0 | 73-21-14 | D06178J | | 9 | | | D05328P | 21 | | | 150-199 |
| 210R | 24 | PW | IJ | 0-0 | 73-21-14 | D06178J | | 9 | | | D05328P | 21 | | | 275-299 |
| 210Z | | | B | 0-0 | 73-21-14 | D06178J | | 18 | | | D05328P | 18 | | | 050-099 |
| 210Z | | | M | 0-0 | 73-21-14 | D06178J | | 18 | | | D05328P | 18 | | | 150-199 |
| 210Z | | | IJ | 0-0 | 73-21-14 | D06178J | | 18 | | | D05328P | 18 | | | 275-299 |
| 212B | 24 | PW | N | 49-11 | SPARE | D04622J | | 38 | | | D05328P | 33 | | | 050-099 |
| 212R | 24 | PW | N | 0-0 | SPARE | D04622J | | 37 | | | D05328P | 34 | | | 050-099 |
| 212Z | | | N | 0-0 | SPARE | D04622J | | 39 | | | D05328P | 35 | | | 050-099 |
| 246 | 20 | UA | | 1-5 | 77-35-11 | D08610 | | | | FC | GD00691 | S.. | 2 | | 050-099 |
| 246 | 20 | UA | | 1-5 | 77-35-11 | D08610 | | | | JU | GD00691 | S.. | 2 | | 275-299 |
| 246B | 24 | PW | JU | 13-5 | 77-35-11 | D08610 | | 9 | | | D05328P | 23 | | | ALL |
| 246R | 24 | PW | JU | 0-0 | 77-35-11 | D08610 | | 8 | | | D05328P | 22 | | | ALL |
| 246Z | | | JU | 0-0 | 77-35-11 | D08610 | | | | FC | D05328P | 37 | | | 050-099 |
| 246Z | | | JU | 0-0 | 77-35-11 | GD00691 | | S.. | 2 | | D05328P | 37 | | | 150-199 |
| 246Z | | | JU | 0-0 | 77-35-11 | D08610 | | | | JU | D05328P | 37 | | | 275-299 |
| 249 | 20 | UA | | 1-5 | 77-35-11 | D08610 | | | | FB | GD00691 | S.. | 2 | | 050-099 |
| 249 | 20 | UA | | 1-5 | 77-35-11 | D08610 | | | | JX | GD00691 | S.. | 2 | | 275-299 |
| 249B | 24 | PW | JX | 13-5 | 77-35-11 | D08610 | | 6 | | | D05328P | 25 | | | ALL |
| 249R | 24 | PW | JX | 0-0 | 77-35-11 | D08610 | | 5 | | | D05328P | 24 | | | ALL |
| 249Z | | | JX | 0-0 | 77-35-11 | D08610 | | | | FB | D05328P | 36 | | | 050-099 |
| 249Z | | | JX | 0-0 | 77-35-11 | GD00691 | | S.. | 2 | | D05328P | 36 | | | 150-199 |
| 249Z | | | JX | 0-0 | 77-35-11 | D08610 | | | | JX | D05328P | 36 | | | 275-299 |
| 302B | 24 | PX | F | 36-1 | 73-31-11 | D05328P | | 30 | | | D06238P | A03 | \$D | | ALL |
| 302R | 24 | PX | F | 0-0 | 73-31-11 | D05328P | | 31 | | | D06238P | A02 | \$D | | ALL |
| 302Y | 24 | PX | F | 0-0 | 73-31-11 | D05328P | | 32 | | | D06238P | A04 | \$D | | ALL |
| 302Z | | | F | 0-0 | 73-31-11 | D05328P | | 29 | | | D06238P | A16 | \$D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|--|-------|-------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0764 | 286T0764 | P61 TO R WING FRONT SPAR-R2B-ENG INSTR/FLT CONT (continued) | | | | | | | | | | | | | |
| 303B | 24 | PM | Q | 61-11 | 79-32-11 | D04622J | | 15 | | | | D06238P | A06 | \$D | 050-099 |
| 303B | 24 | PM | Q | 71-9 | 79-32-11 | D04622J | | 15 | | | | D06238P | A06 | \$D | 150-199, 275-299 |
| 303R | 24 | PM | Q | 0-0 | 79-32-11 | D04622J | | 13 | | | | D06238P | A07 | \$D | ALL |
| 303Y | 24 | PM | Q | 0-0 | 79-32-11 | D04622J | | 14 | | | | D06238P | A05 | \$D | ALL |
| 501 | 22 | PA | | 15-5 | SPARE | D04754P | | 37 | | | | D05328P | 14 | | ALL |
| 502 | 22 | PA | | 49-11 | SPARE | D05328P | | CAP | Y | | | D04622J | 30 | | 050-099 |
| 502 | 22 | PA | | 60-3 | SPARE | D05328P | | CAP | Y | | | D04622J | 30 | | 150-199, 275-276 |
| 502 | 22 | PA | | 60-3 | SPARE | D05328P | | 27 | | | | D04622J | 30 | | 277-278 |
| 503 | 24 | PK | | 22-2 | 78-36-11 | D06238P | | A12 | | | | D05428J | 17 | | 050-099 |
| 503 | 24 | PK | | 22-2 | 78-36-11 | D06238P | | A12 | \$D | | | D05428J | 17 | | 150-199, 275-299 |
| 504 | 24 | PK | | 22-2 | 78-36-11 | D06238P | | A13 | | | | D05428J | 18 | | 050-099 |
| 504 | 24 | PK | | 22-2 | 78-36-11 | D06238P | | A13 | \$D | | | D05428J | 18 | | 150-199, 275-299 |
| 801 | 22 | PA | | 27-7 | SPARE | D04754P | | 38 | | | | D05428J | 12 | | ALL |
| 802 | 22 | PA | | 57-0 | SPARE | D04754P | | 39 | | | | D04622J | 29 | | 050-099 |
| 802 | 22 | PA | | 66-9 | SPARE | D04754P | | 39 | | | | D04622J | 29 | | 150-199, 275-299 |
| 803 | 22 | PA | | 46-5 | SPARE | D05428J | | 13 | | | | D04622J | 31 | | 050-099 |
| 803 | 22 | PA | | 56-9 | SPARE | D05428J | | 13 | | | | D04622J | 31 | | 150-199, 275-299 |
| W0766 | 286T0766 | P61 TO R WING FRONT SPAR-R2A-FLT CONT AND ENG INSTR | | | | | | | | | | | | | |
| 001 | 22 | PA | | 14-0 | 78-36-21 | D05326P | | 5 | | | | D04760P | 9 | | 050-099 |
| 001 | 22 | PA | | 14-0 | 78-36-21 | D04760P | | 9 | | | | D05326P | 5 | | 150-199, 275-299 |
| 002 | 22 | PQ | AB | 48-0 | 78-36-21 | D05326P | | 9 | | | | D04616J | 9 | | 050-099 |
| 002 | 22 | PQ | G | 58-0 | 78-36-21 | D04616J | | 9 | | | | D05326P | 9 | | 150-199 |
| 002 | 22 | PQ | AB | 58-0 | 78-36-21 | D05326P | | 9 | | | | D04616J | 9 | | 275-299 |
| 002Z | | | AB | 0-0 | 78-36-21 | D05326P | | 7 | | | | D04616J | =CC | D | 050-099, 275-299 |
| 002Z | | | G | 0-0 | 78-36-21 | D04616J | | =CC | D | | | D05326P | 7 | | 150-199 |
| 004 | 22 | PA | | 48-0 | 74-31-21 | D04616J | | 4 | | | | D05326P | 6 | | 050-099 |
| 004 | 22 | PA | | 58-0 | 74-31-21 | D04616J | | 4 | | | | D05326P | 6 | | 150-199, 275-299 |
| 005 | 22 | PA | | 48-0 | 79-35-11 | D04616J | | 5 | | | | D05326P | 37 | | 050-099 |
| 005 | 22 | PA | | 58-0 | 79-35-11 | D04616J | | 5 | | | | D05326P | 37 | | 150-199, 275-299 |
| 007 | 20 | PA | | 58-0 | SPARE | D04616J | | CAP | Y | | | D05326P | CAP | Y | 150-199 |
| 009 | 22 | PA | | 48-0 | 79-33-11 | D04616J | | 10 | | | | D05326P | 35 | | 050-099 |
| 009 | 22 | PA | | 58-0 | 79-33-11 | D04616J | | 10 | | | | D05326P | 35 | | 150-199, 275-299 |
| 010 | 22 | PA | | 48-0 | 30-21-11 | D04616J | | 12 | | | | D05326P | 19 | | 050-099 |
| 010 | 22 | PA | | 58-0 | 30-21-11 | D04616J | | 12 | | | | D05326P | 19 | | 150-199, 275-299 |
| 011 | 24 | PK | | 41-0 | 75-23-11 | D04616J | | 14 | | | | SM00001 | 9 | | 050-099 |
| 011 | 24 | PK | | 51-0 | 75-23-11 | D04616J | | 14 | | | | SM00001 | 9 | | 150-199, 275-299 |
| 012 | 22 | PA | | 14-0 | SPARE | D05326P | | CAP | Y | | | D04760P | 19 | | 150-199, 275-299 |
| 013 | 24 | PK | | 48-0 | 30-21-11 | D04616J | | 29 | | | | D05326P | 20 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0760
Page 4
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|-------|------|---------|--------|----|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W0766 | 286T0766 | | | | P61 TO R WING FRONT SPAR-R2A-FLT CONT AND ENG INSTR (continued) | | | | | | | | | | | | | |
| 013 | 24 | | PK | | 58-0 | 30-21-11 | D04616J | | 29 | | | | D05326P | | 20 | | | 150-199, 275-299 |
| 019 | 24 | | PK | | 48-0 | 78-34-21 | D05326P | | 53 | | | | D04616J | | 41 | | | 050-099 |
| 019 | 24 | | PK | | 58-0 | 78-34-21 | D04616J | | 41 | | | | D05326P | | 53 | | | 150-199, 275-299 |
| 01TI | | | | C | 0-0 | 77-31-11 | D04616J | | 28 | | | | D05430J | | 6 | | | 050-099, 155-199, 277-299 |
| 01TO | | | | C | 0-0 | 77-31-11 | D04616J | = CC | | D | | | D05430J | = CC | | D | | 050-099, 155-199 |
| 01TO | | | | C | 0-0 | 77-31-11 | D04616J | = CC | | M | | | D05430J | = CC | | M | | 277-299 |
| 01TR | 20 | | RQ | C | 47-0 | 77-31-11 | D04616J | | 26 | | | | D05430J | | 4 | | | 050-099 |
| 01TR | 20 | | RQ | C | 56-0 | 77-31-11 | D04616J | | 26 | | | | D05430J | | 4 | | | 155-157, 164-199 |
| 01TR | 20 | | RQ | C | 57-0 | 77-31-11 | D04616J | | 26 | | | | D05430J | | 4 | | | 162-163, 277-299 |
| 01TW | 20 | | RQ | C | 0-0 | 77-31-11 | D04616J | | 27 | | | | D05430J | | 5 | | | 050-099, 155-199, 277-299 |
| 020 | 22 | | PA | | 56-0 | SPARE | D04616J | | 52 | | | | D04760P | | 20 | | | 050-099 |
| 020 | 22 | | PA | | 66-0 | SPARE | D04616J | | 52 | | | | D04760P | | 20 | | | 150-199, 275-299 |
| 021 | 22 | | PA | | 66-0 | SPARE | D04616J | | 53 | | | | D04760P | | 21 | | | 150-199, 275-299 |
| 022 | 24 | | PK | | 27-0 | 78-36-21 | D05430J | | 1 | | | | D04760P | | 6 | | | 050-099 |
| 022 | 24 | | PK | | 27-0 | 78-36-21 | D04760P | | 6 | | | | D05430J | | 1 | | | 150-199, 275-299 |
| 023 | 24 | | PK | | 18-0 | 73-21-14 | D06180J | | 28 | | | | D05326P | | 50 | | | ALL |
| 025 | 22 | | PA | | 14-0 | 74-31-21 | D04760P | | 3 | | | | D05326P | | 3 | | | ALL |
| 028 | 22 | | PA | | 48-0 | 30-21-11 | D04616J | | 11 | | | | D05326P | | 21 | | | 050-099 |
| 028 | 22 | | PA | | 58-0 | 30-21-11 | D04616J | | 11 | | | | D05326P | | 21 | | | 150-199, 275-299 |
| 029 | 20 | | PA | | 56-0 | SPARE | D04616J | | 50 | | | | D04760P | | 22 | | | 050-099 |
| 029 | 20 | | PA | | 66-0 | SPARE | D04616J | | 50 | | | | D04760P | | 22 | | | 150-199, 275-299 |
| 030 | 20 | | PA | | 56-0 | SPARE | D04616J | | 51 | | | | D04760P | | 23 | | | 050-099 |
| 030 | 20 | | PA | | 66-0 | SPARE | D04616J | | 51 | | | | D04760P | | 23 | | | 150-199, 275-299 |
| 031 | 20 | | PA | | 56-0 | SPARE | D04616J | | 43 | | | | D04760P | | 24 | | | 050-099 |
| 031 | 20 | | PA | | 66-0 | SPARE | D04616J | | 43 | | | | D04760P | | 24 | | | 150-199, 275-299 |
| 032 | 20 | | PA | | 56-0 | SPARE | D04616J | | 44 | | | | D04760P | | 25 | | | 050-099 |
| 032 | 20 | | PA | | 66-0 | SPARE | D04616J | | 44 | | | | D04760P | | 25 | | | 150-199, 275-299 |
| 033 | 24 | | PK | | 48-0 | 30-21-11 | D05326P | | 22 | | | | D04616J | | 45 | | | 050-099 |
| 033 | 24 | | PK | | 58-0 | 30-21-11 | D05326P | | 22 | | | | D04616J | | 45 | | | 150-199, 275-299 |
| 035 | 24 | | PK | | 48-0 | SPARE | D04616J | | 38 | | | | D05326P | | 30 | | | 050-099 |
| 035 | 24 | | PK | | 58-0 | SPARE | D04616J | | 38 | | | | D05326P | | 30 | | | 150-199, 275-299 |
| 036 | 24 | | PK | | 48-0 | 78-36-21 | D04616J | | 42 | | | | D05326P | | 31 | | | 050-099 |
| 036 | 24 | | PK | | 58-0 | 78-36-21 | D04616J | | 42 | | | | D05326P | | 31 | | | 150-199, 275-299 |
| 037 | 22 | | PA | | 14-0 | 74-31-21 | D04760P | | 1 | | | | D05326P | | 18 | | | ALL |
| 038 | 22 | | PA | | 14-0 | 74-31-21 | D04760P | | 2 | | | | D05326P | | 4 | | | ALL |
| 039 | 22 | | PA | | 14-0 | 27-51-11 | D06182J | | 6 | | | | D04760P | | 33 | | | ALL |
| 040 | 18 | | PA | | 14-0 | 27-51-11 | D06182J | | 7 | DK | | | D04760P | | 34 | DL | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0766 | 286T0766 | | | P61 TO R WING FRONT SPAR-R2A-FLT CONT AND ENG INSTR (continued) | | | | | | | | | | | |
| 041 | 20 | | PA | 14-0 | 27-51-11 | D06182J | | 8 | | | D04760P | | 35 | | ALL |
| 042 | 24 | | PK | 14-0 | 27-51-11 | D06182J | | 9 | | | D04760P | | 36 | | ALL |
| 043 | 24 | | PK | 14-0 | 27-51-11 | D06182J | | 10 | | | D04760P | | 37 | | ALL |
| 044 | 24 | | PK | 14-0 | 27-51-11 | D06182J | | 11 | | | D04760P | | 38 | | ALL |
| 045 | 24 | | PK | 14-0 | 27-51-11 | D06182J | | 12 | | | D04760P | | 39 | | ALL |
| 046 | 24 | | PK | 14-0 | 27-51-11 | D06182J | | 13 | | | D04760P | | 40 | | ALL |
| 047 | 24 | | PK | 14-0 | 27-51-11 | D06182J | | 14 | | | D04760P | | 41 | | ALL |
| 048 | 24 | | PK | 14-0 | 27-51-11 | D06182J | | 15 | | | D04760P | | 42 | | ALL |
| 049 | 24 | | PK | 14-0 | 27-51-11 | D06182J | | 16 | | | D04760P | | 43 | | ALL |
| 050 | 24 | | PK | 14-0 | 27-51-11 | D06180J | | 16 | | | D04760P | | 44 | | ALL |
| 051 | 24 | | PK | 14-0 | 27-51-11 | D06180J | | 17 | | | D04760P | | 45 | | ALL |
| 052 | 24 | | PK | 14-0 | 27-51-11 | D06180J | | 18 | | | D04760P | | 46 | | ALL |
| 053 | 24 | | PK | 14-0 | 27-51-11 | D06180J | | 19 | | | D04760P | | 47 | | ALL |
| 054 | 24 | | PK | 14-0 | 27-51-11 | D06180J | | 20 | | | D04760P | | 48 | | ALL |
| 055 | 24 | | PK | 14-0 | 27-51-11 | D06180J | | 21 | | | D04760P | | 49 | | ALL |
| 056 | 24 | | PK | 14-0 | 27-51-11 | D06180J | | 22 | | | D04760P | | 50 | | ALL |
| 057 | 24 | | PK | 14-0 | 27-51-11 | D06180J | | 23 | | | D04760P | | 51 | | ALL |
| 058 | 24 | | PK | 14-0 | 27-51-11 | D06180J | | 24 | | | D04760P | | 52 | | ALL |
| 059 | 24 | | PK | 14-0 | 27-51-11 | D06180J | | 25 | | | D04760P | | 53 | | ALL |
| 060 | 18 | | PA | 14-0 | 27-81-11 | D06182J | | 17 | DK | | D04760P | | 54 | DL | ALL |
| 061 | 22 | | PA | 18-0 | 27-81-11 | D06182J | | 18 | | | D05326P | | 38 | | ALL |
| 062 | 18 | | PA | 18-0 | 27-81-11 | D06182J | | 19 | DK | | D05326P | | 39 | DK | ALL |
| 063 | 22 | | PA | 18-0 | 27-81-11 | D06182J | | 20 | | | D05326P | | 40 | | ALL |
| 064 | 22 | | PA | 18-0 | 79-33-11 | D06180J | | 15 | | | D05326P | | 36 | | ALL |
| 065 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 1 | | | D04738P | | 18 | | ALL |
| 066 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 2 | | | D04738P | | 19 | | ALL |
| 067 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 3 | | | D04738P | | 27 | | ALL |
| 068 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 4 | | | D04738P | | 28 | | ALL |
| 069 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 5 | | | D04738P | | 29 | | ALL |
| 070 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 6 | | | D04738P | | 30 | | ALL |
| 071 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 7 | | | D04738P | | 31 | | ALL |
| 072 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 8 | | | D04738P | | 26 | | ALL |
| 073 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 9 | | | D04738P | | 25 | | ALL |
| 074 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 10 | | | D04738P | | 20 | | ALL |
| 075 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 11 | | | D04738P | | 24 | | ALL |
| 076 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 12 | | | D04738P | | 21 | | ALL |
| 077 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 13 | | | D04738P | | 50 | | ALL |
| 078 | 24 | | PK | 15-0 | 32-42-12 | D06180J | | 14 | | | D04738P | | 23 | | ALL |
| 079 | 24 | | PV | R | 31-0 | 32-61-14 | D06182J | | 1 | | D05430J | | 21 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0760
Page 6
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|------------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0766 | 286T0766 | | | P61 TO R WING FRONT SPAR-R2A-FLT CONT AND ENG INSTR (continued) | | | | | | | | | | | | |
| 079Z | | | R | 0-0 | 32-61-14 | D06182J | DED | | | | D05430J | DED | | ALL | | |
| 080 | 24 | PK | | 31-0 | 32-61-14 | D06182J | 2 | | | | D05430J | 22 | | ALL | | |
| 081 | 18 | PA | | 14-0 | 27-51-11 | D06182J | 5 | DK | | | D04760P | 32 | DL | ALL | | |
| 082 | 24 | PK | | 17-0 | 75-23-11 | D04760P | 18 | | | | SM00001 | | 9 | ALL | | |
| 083 | 24 | PK | | 48-0 | 75-23-11 | D05326P | 15 | | | | D04616J | 39 | | 050-099 | | |
| 083 | 24 | PK | | 58-0 | 75-23-11 | D05326P | 15 | | | | D04616J | 39 | | 150-199, 275-299 | | |
| 084 | 24 | PK | | 48-0 | 75-23-11 | D05326P | 1 | | | | D04616J | 15 | | 050-099 | | |
| 084 | 24 | PK | | 58-0 | 75-23-11 | D05326P | 1 | | | | D04616J | 15 | | 150-199, 275-299 | | |
| 085 | 24 | PK | | 48-0 | 75-23-11 | D05326P | 17 | | | | D04616J | 40 | | 050-099 | | |
| 085 | 24 | PK | | 58-0 | 75-23-11 | D05326P | 17 | | | | D04616J | 40 | | 150-199, 275-299 | | |
| 086 | 24 | PK | | 9-0 | 75-23-11 | D05326P | 16 | | | | SM00001 | | 9 | ALL | | |
| 088 | 24 | PK | | 57-0 | 73-33-11 | D04738P | 3 | | | | D04616J | 47 | | 050-099 | | |
| 088 | 24 | PK | | 67-0 | 73-33-11 | D04738P | 3 | | | | D04616J | 47 | | 150-199, 275-299 | | |
| 089 | 24 | PK | | 48-0 | 73-33-11 | D05326P | 51 | | | | D04616J | 48 | | 050-099 | | |
| 089 | 24 | PK | | 58-0 | 73-33-11 | D05326P | 51 | | | | D04616J | 48 | | 150-199, 275-299 | | |
| 090 | 24 | PK | | 48-0 | 73-33-11 | D05326P | 52 | | | | D04616J | 49 | | 050-099 | | |
| 090 | 24 | PK | | 58-0 | 73-33-11 | D05326P | 52 | | | | D04616J | 49 | | 150-199, 275-299 | | |
| 091 | 24 | PK | | 14-0 | 78-36-21 | D04760P | 7 | | | | D05326P | 48 | | 050-099, 275-278 | | |
| 091 | 24 | PK | | 14-0 | SPARE | D04760P | 7 | | | | D05326P | 48 | | 150-199, 280-299 | | |
| 092 | 24 | PK | | 14-0 | 78-36-21 | D04760P | 8 | | | | D05326P | 49 | | 050-099, 275-278 | | |
| 092 | 24 | PK | | 14-0 | SPARE | D04760P | 8 | | | | D05326P | 49 | | 150-199, 280-299 | | |
| 093 | 24 | PK | | 14-0 | SPARE | D04760P | 12 | | | | D05326P | 14 | | ALL | | |
| 098 | 22 | PA | | 48-0 | 30-21-11 | D05326P | 8 | | | | D04616J | 8 | | 050-099 | | |
| 098 | 22 | PA | | 58-0 | 30-21-11 | D05326P | 8 | | | | D04616J | 8 | | 150-199, 275-299 | | |
| 100 | 18 | PA | | 14-0 | SPARE | D04760P | 4 | DL | | | D05326P | 10 | DK | ALL | | |
| 101 | 18 | PA | | 14-0 | SPARE | D04760P | 5 | DL | | | D05326P | 2 | DK | ALL | | |
| 102 | 24 | PK | | 31-0 | 31-31-26 | D06182J | 3 | | | | D05430J | 15 | | ALL | | |
| 125 | 24 | PK | | 48-0 | 78-36-21 | D05326P | 55 | | | | D04616J | 13 | | 050-099 | | |
| 125 | 24 | PK | | 58-0 | 78-36-21 | D05326P | 55 | | | | D04616J | 13 | | 150-156, 162-166, 275-276 | | |
| 125 | 24 | PK | | 63-0 | 78-36-21 | D05326P | 55 | | | | D04616J | 13 | | 157, 167-199, 277-299 | | |
| 202B | 24 | PW | IB | 18-0 | 73-21-14 | D06180J | 26 | | | | D05326P | 42 | | 050-099, 275-299 | | |
| 202B | 24 | PW | A | 18-0 | 73-21-14 | D06180J | 26 | | | | D05326P | 42 | | 150-199 | | |
| 202R | 24 | PW | IB | 0-0 | 73-21-14 | D06180J | 27 | | | | D05326P | 43 | | 050-099, 275-299 | | |
| 202R | 24 | PW | A | 0-0 | 73-21-14 | D06180J | 27 | | | | D05326P | 43 | | 150-199 | | |
| 202Z | | | IB | 0-0 | 73-21-14 | D06180J | 31 | | | | D05326P | 41 | | 050-099, 275-299 | | |
| 202Z | | | A | 0-0 | 73-21-14 | D06180J | 31 | | | | D05326P | 41 | | 150-199 | | |
| 204R | 20 | RJ | C | 57-0 | 77-31-11 | D04616J | 26 | | | | D05430J | 4 | | 150-154, 275-276 | | |
| 204W | 20 | RJ | C | 0-0 | 77-31-11 | D04616J | 27 | | | | D05430J | 5 | | 150-154, 275-276 | | |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0766 | 286T0766 | | | P61 TO R WING FRONT SPAR-R2A-FLT CONT AND ENG INSTR (continued) | | | | | | | | | | | |
| 204Z | | | | C | 0-0 | 77-31-11 | D04616J | | 28 | | D05430J | | 6 | | 150-154, 275-276 |
| 205B | 24 | PL | IE | | 47-0 | 78-36-21 | D05430J | | 7 | | D04616J | | 30 | | 050-099 |
| 205B | 24 | PL | D | | 57-0 | 78-36-21 | D04616J | | 30 | | D05430J | | 7 | | 150-199, 275-299 |
| 205R | 24 | PL | IE | | 0-0 | 78-36-21 | D05430J | | 8 | | D04616J | | 31 | | 050-099 |
| 205R | 24 | PL | D | | 0-0 | 78-36-21 | D04616J | | 31 | | D05430J | | 8 | | 150-199, 275-299 |
| 206B | 24 | PL | IF | | 47-0 | 78-36-21 | D05430J | | 9 | | D04616J | | 32 | | 050-099 |
| 206B | 24 | PL | E | | 57-0 | 78-36-21 | D04616J | | 32 | | D05430J | | 9 | | 150-199, 275-299 |
| 206R | 24 | PL | IF | | 0-0 | 78-36-21 | D05430J | | 10 | | D04616J | | 33 | | 050-099 |
| 206R | 24 | PL | E | | 0-0 | 78-36-21 | D04616J | | 33 | | D05430J | | 10 | | 150-199, 275-299 |
| 207B | 24 | PL | IG | | 47-0 | 78-36-21 | D05430J | | 11 | | D04616J | | 34 | | 050-099 |
| 207B | 24 | PL | F | | 57-0 | 78-36-21 | D04616J | | 34 | | D05430J | | 11 | | 150-199, 275-299 |
| 207R | 24 | PL | IG | | 0-0 | 78-36-21 | D05430J | | 12 | | D04616J | | 35 | | 050-099 |
| 207R | 24 | PL | F | | 0-0 | 78-36-21 | D04616J | | 35 | | D05430J | | 12 | | 150-199, 275-299 |
| 208B | 24 | PL | IH | | 47-0 | 78-36-21 | D05430J | | 13 | | D04616J | | 36 | | 050-099 |
| 208B | 24 | PL | U | | 57-0 | 78-36-21 | D04616J | | 36 | | D05430J | | 13 | | 150-199 |
| 208B | 24 | PL | G | | 57-0 | 78-36-21 | D04616J | | 36 | | D05430J | | 13 | | 275-299 |
| 208R | 24 | PL | IH | | 0-0 | 78-36-21 | D05430J | | 14 | | D04616J | | 37 | | 050-099 |
| 208R | 24 | PL | U | | 0-0 | 78-36-21 | D04616J | | 37 | | D05430J | | 14 | | 150-199 |
| 208R | 24 | PL | G | | 0-0 | 78-36-21 | D04616J | | 37 | | D05430J | | 14 | | 275-299 |
| 301B | 24 | PM | Q | | 48-0 | 79-31-11 | D04616J | | 1 | | D05326P | | 34 | | 050-099 |
| 301B | 24 | PM | Q | | 58-0 | 79-31-11 | D04616J | | 1 | | D05326P | | 34 | | 150-199, 275-299 |
| 301R | 24 | PM | Q | | 0-0 | 79-31-11 | D04616J | | 3 | | D05326P | | 33 | | ALL |
| 301Y | 24 | PM | Q | | 0-0 | 79-31-11 | D04616J | | 2 | | D05326P | | 32 | | ALL |
| 302B | 24 | PX | N | | 48-0 | 73-31-11 | D05326P | | 24 | | D04616J | | 24 | | 050-099 |
| 302B | 24 | PX | N | | 58-0 | 73-31-11 | D05326P | | 24 | | D04616J | | 24 | | 150-199 |
| 302B | 24 | PX | MB | | 58-0 | 73-31-11 | D05326P | | 24 | | D04616J | | 24 | | 275-299 |
| 302R | 24 | PX | N | | 0-0 | 73-31-11 | D05326P | | 25 | | D04616J | | 23 | | 050-099, 150-199 |
| 302R | 24 | PX | MB | | 0-0 | 73-31-11 | D05326P | | 25 | | D04616J | | 23 | | 275-299 |
| 302Y | 24 | PX | N | | 0-0 | 73-31-11 | D05326P | | 26 | | D04616J | | 25 | | 050-099, 150-199 |
| 302Y | 24 | PX | MB | | 0-0 | 73-31-11 | D05326P | | 26 | | D04616J | | 25 | | 275-299 |
| 302Z | | | N | | 0-0 | 73-31-11 | D05326P | | 44 | | D04616J | | 22 | | 050-099, 150-199 |
| 302Z | | | MB | | 0-0 | 73-31-11 | D05326P | | 44 | | D04616J | | 22 | | 275-299 |
| 303B | 20 | PC | MC | | 58-0 | SPARE | D05326P | | 28 | | D04616J | CAP | Y | | 150-199, 275-299 |
| 303R | 20 | PC | MC | | 0-0 | SPARE | D05326P | | 27 | | D04616J | CAP | Y | | 150-199, 275-299 |
| 303Y | 20 | PC | MC | | 0-0 | SPARE | D05326P | | 29 | | D04616J | CAP | Y | | 150-199, 275-299 |
| 304B | 20 | PS | MD | | 58-0 | SPARE | D05326P | CAP | Y | | D04616J | CAP | Y | | 150-199 |
| 304R | 20 | PS | MD | | 0-0 | SPARE | D05326P | CAP | Y | | D04616J | CAP | Y | | 150-199 |
| 304Y | 20 | PS | MD | | 0-0 | SPARE | D05326P | CAP | Y | | D04616J | CAP | Y | | 150-199 |
| 304Z | | | MD | | 0-0 | SPARE | D05326P | DED | | | D04616J | DED | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|--|----|-----|-------------|---------|------------------|------|------|--------|-------|------|---------|---------|-------------|------------------------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0766 | 286T0766 | P61 TO R WING FRONT SPAR-R2A-FLT CONT AND ENG INSTR (continued) | | | | | | | | | | | | | | | |
| 305B | 24 | | PM | H | 57-0 | SPARE | D05430J | | 30 | | | | D04616J | CAP | Y | 150-199, 275-299 | |
| 305R | 24 | | PM | H | 0-0 | SPARE | D05430J | | 29 | | | | D04616J | CAP | Y | 150-199, 275-299 | |
| 305Y | 24 | | PM | H | 0-0 | SPARE | D05430J | | 31 | | | | D04616J | CAP | Y | 150-199, 275-299 | |
| 306B | 24 | | PM | I | 57-0 | SPARE | D05430J | | 27 | | | | D04616J | CAP | Y | 150-199, 275-299 | |
| 306R | 24 | | PM | I | 0-0 | SPARE | D05430J | | 26 | | | | D04616J | CAP | Y | 150-199, 275-299 | |
| 306Y | 24 | | PM | I | 0-0 | SPARE | D05430J | | 28 | | | | D04616J | CAP | Y | 150-199, 275-299 | |
| 501 | 22 | | PA | | 27-0 | SPARE | D04760P | | 29 | | | | D05430J | 18 | | 150-199, 275-299 | |
| 502 | 22 | | PA | | 57-0 | SPARE | D05430J | | 20 | | | | D04616J | CAP | Y | 150-199 | |
| 503 | 22 | | PA | | 57-0 | SPARE | D05430J | | 16 | | | | D04616J | CAP | Y | 150-199 | |
| 512 | 20 | | PA | | 5-0 | | 78-34-21 D05326P | | | | | | FV | GD00754 | S.. | 2 | 050-099, 150-156, 162-166, 275-276 |
| 512 | 20 | | PA | | 15-0 | | 78-34-21 D05326P | | | | | | FV | GD00754 | S.. | 2 | 157, 167-199 |
| 512 | 20 | | PA | | 15-0 | | 78-34-21 D05326P | | | | | | FV | GD00754 | S.. | 2 | 277-299 |
| 513 | 18 | | PQ | AA | 48-0 | | 78-34-21 D05326P | | 45 | DK | | | D04616J | 16 | DK | 050-099 | |
| 513 | 18 | | PQ | AA | 58-0 | | 78-34-21 D05326P | | 45 | DK | | | D04616J | 16 | DK | 150-156, 162-166, 275-276 | |
| 513 | 18 | | PQ | AA | 63-0 | | 78-34-21 D05326P | | 45 | DK | | | D04616J | 6 | DK | 157 | |
| 513 | 18 | | PQ | AA | 63-0 | | 78-34-21 D05326P | | 45 | DK | | | D04616J | 16 | DK | 167-199, 277-299 | |
| 513Z | | | | AA | 0-0 | | 78-34-21 D05326P | | | | | | FV | D04616J | =CC | D | ALL |
| 514 | 18 | | PQ | AC | 48-0 | | 78-34-21 D05326P | | 23 | DK | | | D04616J | 7 | DK | 050-099 | |
| 514 | 18 | | PQ | AC | 58-0 | | 78-34-21 D05326P | | 23 | DK | | | D04616J | 7 | DK | 150-156, 162-166, 275-276 | |
| 514 | 18 | | PQ | AC | 63-0 | | 78-34-21 D05326P | | 23 | DK | | | D04616J | 7 | DK | 157, 167-199, 277-299 | |
| 514Z | | | | AC | 0-0 | | 78-34-21 D05326P | | | | | | FV | D04616J | =CC | D | ALL |
| 801 | 24 | | PK | | 31-0 | | 32-61-14 D06182J | | 22 | | | | D05430J | 25 | | ALL | |
| 802 | 22 | | PA | | 56-0 | SPARE | D04760P | | 31 | | | | D04616J | 46 | | 050-099 | |
| 802 | 22 | | PA | | 66-0 | SPARE | D04760P | | 31 | | | | D04616J | 46 | | 150-199, 275-299 | |
| 803 | 22 | | PA | | 57-0 | SPARE | D05430J | | 17 | | | | D04616J | CAP | Y | 150-199 | |
| FRV | | | | | 0-0 | | 78-34-21 D05326P | | | | | | FV | D05326P | 54 | | ALL |
| W0768 | 286T0768 | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR | | | | | | | | | | | | | | | |
| 001 | 24 | | PV | AA | 13-2 | | 73-21-14 D05668P | | 12 | | | | D05316P | 1 | | 050-099, 275-299 | |
| 001 | 24 | | PV | I | 13-2 | | 73-21-14 D05668P | | 12 | | | | D05316P | 1 | | 150-199 | |
| 001Z | | | | AA | 0-0 | | 73-21-14 D05668P | | 29 | | | | D05316P | | | FK | 050-099 |
| 001Z | | | | I | 0-0 | | 73-21-14 D05668P | | 29 | | | | D05316P | | | FK | 150-199 |
| 001Z | | | | AA | 0-0 | | 73-21-14 D05668P | | 29 | | | | D05316P | | | FF | 275-299 |
| 002 | 24 | | PV | AK | 49-1 | | 73-21-11 D05316P | | 29 | | | | D04624J | 8 | | 050-099 | |
| 002 | 24 | | PV | F | 59-9 | | 73-21-11 D05316P | | 29 | | | | D04624J | 8 | | 150-199 | |
| 002 | 24 | | PV | F | 59-9 | | 73-21-11 D04624J | | 8 | | | | D05316P | 29 | | 275-276 | |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | |
| 002 | 24 | | PV | AB | 59-9 | 73-21-11 | D04624J | | 8 | | | | D05316P | 29 | | | 277-299 |
| 002Z | | | | AK | 0-0 | 73-21-11 | D05316P | | 34 | | | | D04624J | = CC | D | | 050-099 |
| 002Z | | | | F | 0-0 | 73-21-11 | D05316P | | 34 | | | | D04624J | = CC | D | | 150-199 |
| 002Z | | | | F | 0-0 | 73-21-11 | D04624J | = CC | L | | | | D05316P | 34 | | | 275-276 |
| 002Z | | | | AB | 0-0 | 73-21-11 | D04624J | = CC | D | | | | D05316P | 34 | | | 277-278 |
| 002Z | | | | AB | 0-0 | 73-21-11 | D04624J | = CC | M | | | | D05316P | 34 | | | 280-299 |
| 004 | 24 | | PV | AI | 49-0 | 73-21-11 | D06260P | | 31 | | | | D04624J | 5 | | | 050-099 |
| 004 | 24 | | PV | AI | 59-8 | 73-21-11 | D04624J | | 5 | | | | D06260P | 31 | | | 150-199 |
| 004 | 24 | | PV | H | 59-8 | 73-21-11 | D04624J | | 5 | | | | D06260P | 31 | | | 275-278 |
| 004 | 24 | | PV | AD | 59-8 | 73-21-11 | D04624J | | 5 | | | | D06260P | 31 | | | 280-299 |
| 004Z | | | | AI | 0-0 | 73-21-11 | D06260P | | | | FH | | D04624J | = CC | D | | 050-099 |
| 004Z | | | | AI | 0-0 | 73-21-11 | D04624J | = CC | D | | | | D06260P | | | FH | 150-199 |
| 004Z | | | | H | 0-0 | 73-21-11 | D04624J | = CC | D | | | | D06260P | | | AS | 275-278 |
| 004Z | | | | AD | 0-0 | 73-21-11 | D04624J | = CC | M | | | | D06260P | | | AS | 280-299 |
| 010 | 22 | | PA | | 13-2 | 27-09-12 | D05668P | | 10 | | | | D06260P | 3 | | | ALL |
| 013 | 16 | | PQ | AM | 56-7 | 73-21-20 | D04624J | | 13 | FM | | | D04758P | 5 | FL | | 050-099 |
| 013 | 16 | | PQ | AM | 66-8 | 73-21-20 | D04758P | | 5 | FL | | | D04624J | 13 | FM | | 150-199 |
| 013 | 20 | | PQ | AM | 66-8 | 73-21-20 | D04624J | | 13 | | | | D04758P | 5 | | | 275-276 |
| 013 | 16 | | PQ | AM | 66-8 | 73-21-20 | D04624J | | 13 | FM | | | D04758P | 5 | FL | | 277-299 |
| 013Z | | | | AM | 0-0 | 73-21-20 | D04624J | = CC | D | | | | GD05396 | S.. | E | | 050-099, 277-278 |
| 013Z | | | | AM | 0-0 | 73-21-20 | GD05396 | S.. | E | | | | D04624J | = CC | D | | 150-199 |
| 013Z | | | | AM | 0-0 | 73-21-20 | D04624J | = CC | L | | | | GD05396 | S.. | E | | 275-276 |
| 013Z | | | | AM | 0-0 | 73-21-20 | D04624J | = CC | M | | | | GD05396 | S.. | E | | 280-299 |
| 014 | 20 | | PA | | 13-2 | 30-34-21 | D05668P | | 23 | | | | D05316P | 25 | | | 050-099 |
| 014 | 20 | | PA | | 13-2 | 30-34-21 | D05316P | | 25 | | | | D05668P | 23 | | | 150-199, 275-299 |
| 015 | 24 | | PK | | 22-0 | SPARE | D04758P | | 1 | | | | D08032P | 1 | | | ALL |
| 016 | 24 | | PK | | 22-0 | 27-58-21 | D04758P | | 2 | | | | D08032P | 2 | | | ALL |
| 017 | 24 | | PK | | 22-0 | 73-21-17 | D04758P | | 3 | | | | D08032P | 3 | | | ALL |
| 018 | 24 | | PK | | 27-8 | 78-34-21 | D04758P | | 4 | | | | D05638J | 7 | | | ALL |
| 019 | 16 | | PQ | AS | 15-2 | 73-21-20 | D04758P | | 40 | FL | | | D06260P | 9 | FL | | ALL |
| 019Z | | | | AS | 0-0 | 73-21-20 | GD05396 | S.. | E | | | | D06260P | | | FH | 050-099, 150-199 |
| 019Z | | | | AS | 0-0 | 73-21-20 | GD05396 | S.. | E | | | | D06260P | | | AS | 275-299 |
| 020 | 24 | | PV | AT | 22-2 | 73-21-11 | D06258P | | 5 | | | | D08032P | 48 | | | 050-099, 150-199 |
| 020 | 22 | | PQ | E | 22-2 | 73-21-11 | D08032P | | 48 | | | | D06258P | 5 | | | 275-276 |
| 020 | 24 | | PV | AT | 22-2 | 73-21-11 | D08032P | | 48 | | | | D06258P | 5 | | | 277-299 |
| 020Z | | | | AT | 0-0 | 73-21-11 | D06258P | | | | FF | | D08032P | | | FM | 050-099, 150-199 |
| 020Z | | | | E | 0-0 | 73-21-11 | D08032P | | | | FC | | D06258P | | | FH | 275-276 |
| 020Z | | | | AT | 0-0 | 73-21-11 | D08032P | | | | FC | | D06258P | | | FH | 277-299 |
| 021 | 18 | | PA | | 25-5 | 27-51-11 | D05668P | | 1 | DK | | | D04758P | 7 | DL | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | |
| 022 | 22 | | PA | 25-5 | 27-51-11 | D05668P | | 2 | | | | | D04758P | 8 | | | ALL |
| 023 | 18 | | PA | 25-5 | 27-51-11 | D05668P | | 3 | DK | | | | D04758P | 9 | DL | | ALL |
| 024 | 20 | | PA | 25-5 | 27-51-11 | D05668P | | 4 | | | | | D04758P | 10 | | | ALL |
| 025 | 18 | | PA | 15-2 | 27-81-11 | D05316P | | 31 | DK | | | | D04758P | 11 | DL | | ALL |
| 026 | 24 | | PK | 15-0 | 73-21-18 | D05316P | | 30 | | | | | D08032P | 6 | | | ALL |
| 028 | 24 | | PV | 49-0 | 73-21-11 | D04624J | | 4 | | | | | D06260P | 10 | | | 050-099 |
| 028 | 24 | | PV | 53-7 | 73-21-11 | D04624J | | 4 | | | | | SM00027 | | S | | 150-157 |
| 028 | 24 | | PV | 59-8 | 73-21-11 | D04624J | | 4 | | | | | D06260P | 10 | | | 162-199 |
| 028 | 24 | | PV | 53-7 | 73-21-11 | D04624J | | 4 | | | | | SM00027 | | S | | 275 |
| 028 | 24 | | PV | 59-8 | 73-21-11 | D04624J | | 4 | | | | | D06260P | 10 | | | 276-299 |
| 028Z | | | | 0-0 | 73-21-11 | D04624J | | =CC | D | | | | D06260P | | | FH | 050-099, 162-199 |
| 028Z | | | | 0-0 | 73-21-11 | D04624J | | =CC | D | | | | SM00027 | REF | | FJ | 150-157 |
| 028Z | | | | 0-0 | 73-21-11 | D04624J | | =CC | L | | | | SM00027 | REF | V | | 275 |
| 028Z | | | | 0-0 | 73-21-11 | D04624J | | =CC | D | | | | D06260P | | | AS | 276-278 |
| 028Z | | | | 0-0 | 73-21-11 | D04624J | | =CC | M | | | | D06260P | | | AS | 280-299 |
| 029 | 18 | | PA | 15-2 | 27-81-21 | D05316P | | 38 | DK | | | | D04758P | 15 | DL | | ALL |
| 030 | 16 | | PQ | 43-5 | 73-21-11 | D04624J | | 6 | FM | | | | SP04056 | 9 | | | 050-099 |
| 030 | 16 | | PQ | 54-0 | 73-21-11 | SP04056 | | | S | | | | D04624J | 6 | FM | | 150-154 |
| 030 | 16 | | PQ | 54-0 | 73-21-11 | SP04056 | | | 9 | | | | D04624J | 6 | FM | | 155-199 |
| 030 | 16 | | PQ | 68-0 | 73-21-11 | SP04056 | | | S | | | | D04624J | 6 | FM | | 275-276 |
| 030 | 16 | | PQ | 54-0 | 73-21-11 | SP04056 | | | 9 | | | | D04624J | 6 | FM | | 277-299 |
| 030Z | | | | 0-0 | 73-21-11 | D04624J | | =CC | D | | | | SP04056 | REF | V | | 050-099 |
| 030Z | | | | 0-0 | 73-21-11 | SP04056 | | | S | | | | D04624J | =CC | D | | 150-154 |
| 030Z | | | | 0-0 | 73-21-11 | SP04056 | | REF | V | | | | D04624J | =CC | M | | 155-156, 162-166 |
| 030Z | | | | 0-0 | 73-21-11 | SP04056 | | REF | V | | | | D04624J | =CC | D | | 157, 167-199 |
| 030Z | | | | 0-0 | 73-21-11 | SP04056 | | REF | V | | | | D04624J | =CC | D | | 275-278 |
| 030Z | | | | 0-0 | 73-21-11 | SP04056 | | REF | V | | | | D04624J | =CC | M | | 280-299 |
| 033 | 24 | | PK | 25-0 | 27-51-61 | D04758P | | 19 | | | | | D05622J | 15 | | | ALL |
| 034 | 24 | | PK | 25-0 | 27-51-61 | D04758P | | 20 | | | | | D05622J | 16 | | | ALL |
| 035 | 24 | | PK | 25-0 | 27-51-11 | D04758P | | 21 | | | | | D05622J | 17 | | | ALL |
| 036 | 24 | | PK | 25-0 | 27-51-11 | D04758P | | 22 | | | | | D05622J | 18 | | | ALL |
| 037 | 24 | | PK | 25-0 | 27-51-11 | D04758P | | 23 | | | | | D05622J | 19 | | | ALL |
| 038 | 24 | | PK | 25-0 | 27-51-11 | D04758P | | 24 | | | | | D05622J | 20 | | | ALL |
| 039 | 24 | | PK | 25-0 | 27-51-11 | D04758P | | 25 | | | | | D05622J | 21 | | | ALL |
| 040 | 24 | | PK | 25-0 | 27-51-11 | D04758P | | 26 | | | | | D05622J | 22 | | | ALL |
| 041 | 24 | | PK | 25-0 | 27-51-11 | D04758P | | 27 | | | | | D05622J | 23 | | | ALL |
| 042 | 24 | | PK | 25-0 | 27-51-11 | D04758P | | 28 | | | | | D05622J | 24 | | | ALL |
| 043 | 24 | | PK | 15-2 | 78-34-21 | D04758P | | 29 | | | | | D05316P | 23 | | | ALL |
| 044 | 20 | | PA | 74-6 | 27-13-11 | D05416P | | 1 | | | | | D05514J | 12 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 044 | 20 | | PA | | 84-9 | 27-13-11 | D05416P | | | | D05514J | | | | 150-199, 275-299 |
| 045 | 20 | | PA | | 74-6 | 27-13-11 | D05416P | | | | D05514J | | | | 050-099 |
| 045 | 20 | | PA | | 84-9 | 27-13-11 | D05416P | | | | D05514J | | | | 150-199, 275-299 |
| 046 | 22 | | PA | | 74-6 | 27-13-11 | D05416P | | | | D05514J | | | | 050-099 |
| 046 | 22 | | PA | | 84-9 | 27-13-11 | D05416P | | | | D05514J | | | | 150-199, 275-299 |
| 047 | 22 | | PA | | 15-0 | 27-23-11 | D05416P | | | | D06260P | | | | ALL |
| 048 | 20 | | PA | | 15-1 | 27-23-11 | D05416P | | | | D05316P | | | | ALL |
| 049 | 20 | | PA | | 15-0 | 27-23-11 | D05416P | | | | D06260P | | | | ALL |
| 050 | 24 | | PV | BG | 56-9 | 73-21-11 | D04624J | | | | D06258P | | | | 050-099 |
| 050 | 24 | | PV | BG | 66-11 | 73-21-11 | D06258P | | | | D04624J | | | | 150-199 |
| 050 | 24 | | PV | BB | 66-11 | 73-21-11 | D04624J | | | | D06258P | | | | 275-278 |
| 050 | 24 | | PV | BY | 66-11 | 73-21-11 | D04624J | | | | D06258P | | | | 280-299 |
| 050Z | | | | BG | 0-0 | 73-21-11 | D04624J | = CC | D | | D06258P | | | FF | 050-099 |
| 050Z | | | | BG | 0-0 | 73-21-11 | D06258P | | | FF | D04624J | = CC | D | | 150-199 |
| 050Z | | | | BB | 0-0 | 73-21-11 | D04624J | = CC | D | | D06258P | | | FH | 275-278 |
| 050Z | | | | BY | 0-0 | 73-21-11 | D04624J | = CC | M | | D06258P | | | FH | 280-299 |
| 051 | 22 | | PQ | AF | 22-2 | 73-21-11 | D08032P | | | | D06258P | | 15 | | 050-099 |
| 051 | 22 | | PQ | AF | 22-2 | 73-21-11 | D06258P | | | | D08032P | | 5 | | 150-199 |
| 051 | 22 | | PQ | CA | 22-2 | 73-21-11 | D08032P | | | | D06258P | | 15 | | 275-276 |
| 051 | 24 | | PV | CA | 22-2 | 73-21-11 | D08032P | | | | D06258P | | 15 | | 277-299 |
| 051Z | | | | AF | 0-0 | 73-21-11 | D08032P | | | FM | D06258P | | | FF | 050-099 |
| 051Z | | | | AF | 0-0 | 73-21-11 | D06258P | | | FF | D08032P | | | FM | 150-199 |
| 051Z | | | | CA | 0-0 | 73-21-11 | D08032P | | | FC | D06258P | | | FH | 275-299 |
| 052 | 24 | | PK | | 20-8 | 78-34-21 | D05316P | | | | D05638J | | 3 | | ALL |
| 053 | 24 | | PK | | 15-2 | 31-41-13 | D05316P | | | | D04758P | | 55 | | ALL |
| 054 | 24 | | PK | | 22-6 | 78-34-21 | D08116P | | | | D05316P | | 3 | | 050-099 |
| 054 | 24 | | PK | | 22-6 | 78-34-21 | D05316P | | | | D08116P | | 3 | | 150-199, 275-299 |
| 055 | 24 | | PK | | 22-6 | 78-34-21 | D08116P | | | | D05316P | | 55 | | ALL |
| 056 | 22 | | PA | | 32-8 | 27-62-11 | D08116P | | | | D05668P | | 37 | | ALL |
| 063 | 24 | | PK | | 22-0 | 73-21-15 | D08032P | | | | D04758P | | 53 | | ALL |
| 064 | 24 | | PK | | 15-0 | SPARE | D08032P | | | | D05316P | | CAP | Y | ALL |
| 065 | 22 | | PA | | 15-0 | 73-21-19 | D08032P | | | | D05316P | | 7 | | ALL |
| 067 | 22 | | PA | | 25-5 | 33-51-11 | D04758P | | | | D05668P | | 28 | | ALL |
| 071 | 22 | | PA | | 28-2 | 27-51-11 | D05668P | | | | D05622J | | 1 | | ALL |
| 072 | 22 | | PA | | 28-2 | 27-51-11 | D05668P | | | | D05622J | | 2 | | ALL |
| 073 | 22 | | PA | | 28-2 | 27-51-11 | D05668P | | | | D05622J | | 3 | | ALL |
| 074 | 22 | | PA | | 18-0 | 27-81-11 | D05316P | | | | D05622J | | 4 | | ALL |
| 075 | 22 | | PA | | 18-0 | 27-81-11 | D05316P | | | | D05622J | | 5 | | ALL |
| 076 | 22 | | PA | | 18-0 | 27-81-11 | D05316P | | | | D05622J | | 6 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0760
 Page 12
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | |
| 077 | 22 | | PA | 18-0 | 27-81-21 | D05316P | | 35 | | | | | D05622J | 7 | | | ALL |
| 078 | 22 | | PA | 18-0 | 27-81-21 | D05316P | | 36 | | | | | D05622J | 8 | | | ALL |
| 079 | 22 | | PA | 18-0 | 27-81-21 | D05316P | | 11 | | | | | D05622J | 9 | | | ALL |
| 080 | 22 | | PA | 49-1 | 27-81-11 | D05316P | | 42 | | | | | D05712J | 1 | | | 050-099 |
| 080 | 22 | | PA | 59-8 | 27-81-11 | D05316P | | 42 | | | | | D05712J | 1 | | | 150-199, 275-299 |
| 081 | 18 | | PA | 49-1 | 27-81-11 | D05316P | | 43 | DK | | | | D05712J | 2 | DK | | 050-099 |
| 081 | 18 | | PA | 59-8 | 27-81-11 | D05316P | | 43 | DK | | | | D05712J | 2 | DK | | 150-199, 275-299 |
| 082 | 22 | | PA | 45-4 | 27-81-11 | D05316P | | 44 | | | | | SP01914 | 9 | | | 050-099 |
| 082 | 22 | | PA | 56-1 | 27-81-11 | D05316P | | 44 | | | | | SP01914 | 9 | | | 150-199, 275-299 |
| 083 | 18 | | PA | 11-7 | 27-81-11 | SP01914 | | | 9 | | | | D05712J | 3 | DK | | 050-099 |
| 083 | 18 | | PA | 11-9 | 27-81-11 | SP01914 | | | 9 | | | | D05712J | 3 | DK | | 150-199, 275-299 |
| 087 | 22 | | PA | 7-1 | 32-45-11 | D08018P | | 8 | | | | | D05668P | 30 | | | 050-099, 275-299 |
| 087 | 22 | | PA | 7-1 | 32-45-11 | D05668P | | 30 | | | | | D08018P | 8 | | | 150-199 |
| 090 | 24 | | PK | 25-2 | 73-21-12 | D08032P | | 29 | | | | | D05668P | 8 | | | ALL |
| 091 | 24 | | PK | 25-2 | 73-21-16 | D08032P | | 35 | | | | | D05668P | 9 | | | ALL |
| 092 | 24 | | PK | 15-0 | 73-21-17 | D08032P | | 31 | | | | | D05316P | 45 | | | ALL |
| 093 | 22 | | PA | 32-8 | 27-62-11 | D08116P | | 21 | | | | | D05668P | 18 | | | ALL |
| 094 | 20 | | PA | 22-0 | 73-21-19 | D08032P | | 33 | | | | | D04758P | 30 | | | ALL |
| 095 | 22 | | PA | 14-11 | 73-21-19 | D08032P | | 32 | | | | | D06260P | 27 | | | ALL |
| 096 | 20 | | PQ | DU | 14-11 | 73-21-19 | D08032P | 43 | | | | | D06260P | 30 | | | 050-099, 275-299 |
| 096 | 20 | | PQ | WW | 14-11 | 73-21-19 | D08032P | 43 | | | | | D06260P | 30 | | | 150-199 |
| 096Z | | | | DU | 0-0 | 73-21-19 | D08032P | 44 | | | | | D06260P | 11 | | | 050-099, 275-299 |
| 096Z | | | | WW | 0-0 | 73-21-19 | D08032P | 44 | | | | | D06260P | 11 | | | 150-199 |
| 097 | 24 | | PK | | 22-0 | SPARE | D08032P | 30 | | | | | D04758P | 31 | | | 150-199 |
| 097 | 24 | | PK | | 22-0 | 73-21-16 | D08032P | 30 | | | | | D04758P | 31 | | | 275-299 |
| 100 | 20 | | PQ | AC | 49-1 | 73-21-19 | D05316P | 52 | | | | | D04624J | 40 | | | 050-099 |
| 100 | 20 | | PQ | WR | 59-9 | 73-21-19 | D05316P | 52 | | | | | D04624J | 40 | | | 150-199 |
| 100 | 20 | | PQ | DY | 59-9 | 73-21-19 | D04624J | 40 | | | | | D05316P | 52 | | | 275-299 |
| 100Z | | | | AC | 0-0 | 73-21-19 | D05316P | 6 | | | | | D04624J | =CC | D | | 050-099 |
| 100Z | | | | WR | 0-0 | 73-21-19 | D05316P | 6 | | | | | D04624J | =CC | D | | 150-199 |
| 100Z | | | | DY | 0-0 | 73-21-19 | D04624J | =CC | L | | | | D05316P | 6 | | | 275-276 |
| 100Z | | | | DY | 0-0 | 73-21-19 | D04624J | =CC | D | | | | D05316P | 6 | | | 277-278 |
| 100Z | | | | DY | 0-0 | 73-21-19 | D04624J | =CC | M | | | | D05316P | 6 | | | 280-299 |
| 108 | 22 | | PA | | 22-6 | 28-22-21 | D08116P | 11 | | | | | D05316P | 58 | | | ALL |
| 10A | 18 | | PQ | A | 59-10 | 78-34-21 | D05668P | 41 | DK | | | | D05712J | 10 | DK | | 050-099 |
| 10A | 18 | | PQ | A | 69-10 | 78-34-21 | D05668P | 41 | DK | | | | D05712J | 10 | DK | | 150-199, 275-299 |
| 10AZ | | | | A | 0-0 | 78-34-21 | D05668P | | | | FQ | | D05712J | =CC | C | | 050-099, 150-199, 275-278 |
| 10AZ | | | | A | 0-0 | 78-34-21 | D05668P | | | | FQ | | D05712J | =CC | L | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | |
| 10B | 18 | PQ | F0 | 59-10 | 78-34-21 | D05668P | 40 | DK | | D05712J | 9 | DK | | 050-099 | | |
| 10B | 18 | PQ | F0 | 69-10 | 78-34-21 | D05668P | 40 | DK | | D05712J | 9 | DK | | 150-156, 162-166, 275-276 | | |
| 10B | 18 | PQ | AK | 69-10 | 78-34-21 | D05668P | 40 | DK | | D05712J | 9 | DK | | 157, 167-199, 277-299 | | |
| 10BZ | | | F0 | 0-0 | 78-34-21 | D05668P | | | FQ | D05712J | =CC | C | | 050-099, 150-156, 162-166, 275-276 | | |
| 10BZ | | | AK | 0-0 | 78-34-21 | D05668P | | | FQ | D05712J | =CC | C | | 157, 167-199, 277-278 | | |
| 10BZ | | | AK | 0-0 | 78-34-21 | D05668P | | | FQ | D05712J | =CC | L | | 280-299 | | |
| 10C | 18 | PQ | F1 | 24-7 | 78-34-21 | D04758P | 54 | DL | | D01404 | 21 | DK | | 050-099, 150-199, 275-276 | | |
| 10C | 18 | PQ | AF | 24-7 | 78-34-21 | D04758P | 54 | DL | | D01404 | 21 | DK | | 277-299 | | |
| 10CZ | | | F1 | 0-0 | 78-34-21 | D04758P | | | FA | D01404 | | | FB | 050-099, 150-199, 275-276 | | |
| 10CZ | | | AF | 0-0 | 78-34-21 | D04758P | | | FA | D01404 | | | FB | 277-299 | | |
| 10D | 18 | PQ | F2 | 24-7 | 78-34-21 | D04758P | 17 | DL | | D01404 | 23 | DK | | 050-099 | | |
| 10D | 18 | PQ | D | 24-7 | 78-34-21 | D04758P | 17 | DL | | D01404 | 23 | DK | | 150-199 | | |
| 10D | 18 | PQ | AG | 24-7 | 78-34-21 | D04758P | 17 | DL | | D01404 | 23 | DK | | 275-299 | | |
| 10DZ | | | F2 | 0-0 | 78-34-21 | D04758P | | | FA | D01404 | | | FB | 050-099 | | |
| 10DZ | | | D | 0-0 | 78-34-21 | D04758P | | | FA | D01404 | | | FB | 150-199 | | |
| 10DZ | | | AG | 0-0 | 78-34-21 | D04758P | | | FA | D01404 | | | FB | 275-299 | | |
| 10E | 20 | PA | | 4-0 | 78-34-21 | D01404 | | | FB | GD00649 | S.. | 2 | | 050-099 | | |
| 10E | 20 | PA | | 15-0 | 78-34-21 | D01404 | | | FB | GD00649 | S.. | 2 | | 150-199, 280-299 | | |
| 10E | 20 | PA | | 70-0 | 78-34-21 | D01404 | | | FB | GD00649 | S.. | 2 | | 275-276 | | |
| 10E | 20 | PA | | 15-0 | 78-34-21 | D01404 | | | FB | GD00649 | S.. | E | | 277-278 | | |
| 10F | 18 | PQ | F3 | 59-10 | 78-34-21 | D05668P | 16 | DK | | D05712J | 11 | DK | | 050-099 | | |
| 10F | 18 | PQ | AQ | 69-10 | 78-34-21 | D05668P | 16 | DK | | D05712J | 11 | DK | | 150-156, 162-166 | | |
| 10F | 18 | PQ | F3 | 69-10 | 78-34-21 | D05668P | 16 | DK | | D05712J | 11 | DK | | 157, 167-199 | | |
| 10F | 18 | PQ | AL | 69-10 | 78-34-21 | D05668P | 16 | DK | | D05712J | 11 | DK | | 275-299 | | |
| 10FZ | | | F3 | 0-0 | 78-34-21 | D05668P | | | FQ | D05712J | =CC | C | | 050-099, 157, 167-199 | | |
| 10FZ | | | AQ | 0-0 | 78-34-21 | D05668P | | | FQ | D05712J | =CC | C | | 150-156, 162-166 | | |
| 10FZ | | | AL | 0-0 | 78-34-21 | D05668P | | | FQ | D05712J | =CC | C | | 275-278 | | |
| 10FZ | | | AL | 0-0 | 78-34-21 | D05668P | | | FQ | D05712J | =CC | L | | 280-299 | | |
| 10G | 18 | PQ | F4 | 59-10 | 78-34-21 | D05668P | 17 | DK | | D05712J | 12 | DK | | 050-099 | | |
| 10G | 18 | PQ | F4 | 69-10 | 78-34-21 | D05668P | 17 | DK | | D05712J | 12 | DK | | 150-199, 275-276 | | |
| 10G | 18 | PQ | AH | 69-10 | 78-34-21 | D05668P | 17 | DK | | D05712J | 12 | DK | | 277-278 | | |
| 10G | 18 | PQ | AC | 69-10 | 78-34-21 | D05668P | 17 | DK | | D05712J | 12 | DK | | 280-299 | | |
| 10GZ | | | F4 | 0-0 | 78-34-21 | D05668P | | | FQ | D05712J | =CC | C | | 050-099, 150-199, 275-276 | | |
| 10GZ | | | AH | 0-0 | 78-34-21 | D05668P | | | FQ | D05712J | =CC | C | | 277-278 | | |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | |
| 10GZ | | | | AC | 0-0 | 78-34-21 | D05668P | | | | FQ | D05712J | =CC | L | | 280-299 |
| 10H | 20 | PA | | | 4-0 | 78-34-21 | D08116P | | 5 | | | GD00591 | D.. | 2 | | 050-099, 150-156, 162-166, 275-276 |
| 10H | 20 | PA | | | 15-0 | 78-34-21 | D08116P | | 5 | | | GD00591 | D.. | 2 | | 157, 167-199, 277-299 |
| 110 | 22 | PA | | | 30-10 | SPARE | D05668P | | 7 | | | D05638J | | 9 | | ALL |
| 111 | 24 | PK | | | 14-11 | 21-51-21 | D08032P | | 38 | | | D06260P | | 12 | | ALL |
| 113 | 18 | PA | | | 2-3 | 27-51-41 | D01548 | | 7 | | | GD03348 | S.. | E | | 050-099 |
| 113 | 18 | PA | | | 2-4 | 27-51-41 | D01548 | | 7 | | | GD03348 | S.. | E | | 150-199, 275-299 |
| 116 | 24 | PK | | | 15-5 | 32-42-12 | D01404 | | 1 | | | D08116P | | 7 | | ALL |
| 117 | 24 | PK | | | 15-5 | 32-42-12 | D01404 | | 2 | | | D08116P | | 8 | | ALL |
| 118 | 24 | PK | | | 21-3 | 32-42-12 | D04758P | | 32 | | | D08116P | | 9 | | ALL |
| 119 | 24 | PK | | | 21-3 | 32-42-12 | D04758P | | 33 | | | D08116P | | 14 | | ALL |
| 120 | 24 | PK | | | 15-5 | 32-42-12 | D01404 | | 4 | | | D08116P | | 15 | | ALL |
| 121 | 24 | PK | | | 15-5 | 32-42-12 | D01404 | | 5 | | | D08116P | | 16 | | ALL |
| 122 | 24 | PK | | | 21-3 | 32-42-12 | D04758P | | 34 | | | D08116P | | 17 | | ALL |
| 124 | 24 | PK | | | 15-5 | 31-51-42 | D01404 | | 9 | | | D08116P | | 19 | | ALL |
| 125 | 20 | PA | | | 13-2 | SPARE | D05668P | | | CAP | Y | D05316P | | 5 | | 150-156, 162-166 |
| 125 | 20 | PA | | | 13-2 | SPARE | D05668P | | | CAP | Y | D05316P | CAP | Y | | 157, 167-199 |
| 127 | 20 | PA | | | 1-3 | 31-51-42 | D01404 | | 10 | | | GD03816 | D.. | E | | ALL |
| 128 | 18 | PA | | | 13-5 | 33-13-18 | D08116P | | 10 | | DK | SP02288 | | 9 | | 050-099 |
| 128 | 18 | PA | | | 11-0 | 33-13-18 | D08116P | | 10 | | DK | SP02288 | | 9 | | 150-199, 275-299 |
| 135 | 24 | PK | | | 14-11 | 21-58-11 | D06260P | | 13 | | | D08032P | | 37 | | ALL |
| 136 | 24 | PK | | | 15-0 | 21-58-11 | D06260P | | 14 | | | D05416P | | 18 | | ALL |
| 137 | 16 | PA | | | 14-11 | 21-58-11 | D08032P | | 40 | | FM | D06260P | | 8 | | ALL |
| 138 | 24 | PK | | | 15-0 | 21-58-11 | D06260P | | 16 | | | D05416P | | 24 | | ALL |
| 141 | 24 | PK | | | 14-11 | SPARE | D08032P | | 42 | | | D06260P | CAP | Y | | 050-099 |
| 142 | 20 | UA | | | 1-3 | 73-21-13 | D05966J | | | | | GD00561 | S.. | 2 | | 050-099, 150-156, 162-166 |
| 142 | 20 | UA | | | 0-6 | 73-21-13 | D05966J | | | | | GD00561 | S.. | 2 | | 275-276 |
| 143 | 20 | UA | | | 1-3 | 73-21-13 | D05966J | | | | | GD00561 | S.. | 2 | | 050-099, 150-156, 162-166 |
| 145 | 24 | PK | | | 28-2 | 77-35-11 | D05668P | | 11 | | | D05622J | | 41 | | ALL |
| 146 | 24 | PK | | | 18-0 | 77-35-11 | D05316P | | 60 | | | D05622J | | 42 | | ALL |
| 147 | 24 | PK | | | 49-1 | 24-11-21 | D06588J | | 4 | | | D05316P | | 61 | | 050-099 |
| 147 | 22 | PA | | | 59-9 | 24-11-21 | D05316P | | 61 | | | D06588J | | 4 | | 150-199, 275-278 |
| 147 | 24 | PK | | | 59-9 | 24-11-21 | D05316P | | 61 | | | D06588J | | 4 | | 280-299 |
| 148 | 24 | PK | | | 49-1 | 24-11-21 | D06588J | | 1 | | | D05316P | | 50 | | 050-099 |
| 148 | 24 | PK | | | 59-9 | 24-11-21 | D05316P | | 50 | | | D06588J | | 1 | | 150-199, 275-299 |
| 149 | 24 | PK | | | 49-1 | 24-11-21 | D06588J | | 3 | | | D05316P | | 59 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 149 | 24 | | PK | 59-9 | 24-11-21 | D05316P | 59 | | | D06588J | 3 | | | 150-199, 275-299 | |
| 150 | 24 | | PK | 24-8 | 27-51-11 | D04758P | 35 | | | D06140J | 1 | | | ALL | |
| 151 | 24 | | PK | 24-8 | 27-51-11 | D04758P | 36 | | | D06140J | 2 | | | ALL | |
| 152 | 24 | | PK | 24-8 | 27-51-11 | D04758P | 37 | | | D06140J | 3 | | | ALL | |
| 153 | 24 | | PK | 24-8 | 27-51-11 | D04758P | 41 | | | D06140J | 4 | | | ALL | |
| 154 | 24 | | PK | 24-8 | 27-51-11 | D04758P | 42 | | | D06140J | 5 | | | ALL | |
| 155 | 24 | | PK | 24-8 | 27-51-11 | D04758P | 43 | | | D06140J | 6 | | | ALL | |
| 156 | 24 | | PK | 24-8 | 27-51-11 | D04758P | 44 | | | D06140J | 7 | | | ALL | |
| 157 | 24 | | PK | 24-8 | 27-51-11 | D04758P | 45 | | | D06140J | 8 | | | ALL | |
| 158 | 24 | | PK | 24-8 | 27-51-11 | D04758P | 46 | | | D06140J | 9 | | | ALL | |
| 159 | 24 | | PK | 24-8 | 27-51-11 | D04758P | 47 | | | D06140J | 10 | | | ALL | |
| 160 | 22 | | PA | 28-2 | 27-51-11 | D05622J | 27 | | | D05668P | 19 | | | ALL | |
| 161 | 22 | | PA | 18-0 | 27-81-11 | D05622J | 50 | | | D05316P | 28 | | | ALL | |
| 162 | 22 | | PA | 18-0 | 27-81-21 | D05622J | 51 | | | D05316P | 2 | | | ALL | |
| 163 | 24 | | PK | 25-3 | 24-51-52 | D05416P | 27 | | | D05668P | 20 | | | ALL | |
| 164 | 24 | | PK | 17-11 | 24-51-52 | D06260P | 17 | | | D05622J | 53 | | | ALL | |
| 166 | 24 | | PK | 13-2 | 24-51-52 | D06260P | 18 | | | D05668P | 21 | | | ALL | |
| 172 | 24 | | PK | 27-8 | 74-31-21 | D04758P | 48 | | | D05638J | 24 | | | ALL | |
| 173 | 24 | | PK | 14-11 | 21-51-21 | D08032P | 4 | | | D06260P | 23 | | | ALL | |
| 174 | 22 | | PA | 18-0 | 27-81-11 | D05622J | 54 | | | D05316P | 48 | | | ALL | |
| 175 | 22 | | PA | 18-0 | 27-81-11 | D05622J | 55 | | | D05316P | 49 | | | ALL | |
| 177 | 20 | | PA | 27-6 | 33-43-11 | D05416P | 29 | | | D05638J | 16 | | | 050-099 | |
| 177 | 18 | | PA | 27-6 | 33-43-11 | D05416P | 10 | DL | | D05638J | 16 | DK | | 150-199, 275-299 | |
| 178 | 22 | | PA | 15-0 | SPARE | D08032P | 41 | | | D05316P | CAP | Y | | 050-099 | |
| 178 | 22 | | PA | 15-0 | SPARE | D08032P | 41 | | | D05316P | 40 | | | 150-199, 275-299 | |
| 179 | 22 | | PA | 15-0 | 73-21-19 | D08032P | 53 | | | D05316P | 41 | | | ALL | |
| 180 | 22 | | PA | 13-2 | SPARE | D05668P | 26 | | | D06260P | CAP | Y | | 050-099 | |
| 180 | 22 | | PA | 13-2 | SPARE | D06260P | CAP | Y | | D05668P | 26 | | | 150-199, 280-299 | |
| 180 | 22 | | PA | 13-2 | SPARE | D06260P | CAP | Y | | D05668P | 26 | Y | | 275-278 | |
| 181 | 24 | | PK | 13-2 | SPARE | D05668P | 25 | | | D06260P | CAP | Y | | 050-099 | |
| 181 | 24 | | PK | 13-2 | SPARE | D06260P | CAP | Y | | D05668P | 25 | | | 150-199, 275-299 | |
| 182 | 24 | | PK | 25-5 | 78-36-21 | D04758P | 6 | | | D05668P | 24 | | | ALL | |
| 183 | 22 | | PQ | HH | 34-11 | 78-36-11 | D08116P | 20 | | D05638J | 4 | | | 050-099 | |
| 183 | 22 | | PQ | BF | 34-11 | 78-36-11 | D05638J | 4 | | D08116P | 20 | | | 150-199, 275-278 | |
| 183 | 22 | | PQ | HH | 34-11 | 78-36-11 | D05638J | 4 | | D08116P | 20 | | | 280-299 | |
| 183Z | | | | HH | 0-0 | 78-36-11 | D08116P | DED | | D05638J | DED | | | 050-099 | |
| 183Z | | | | BF | 0-0 | 78-36-11 | D05638J | DED | | D08116P | DED | | | 150-199, 275-278 | |
| 183Z | | | | HH | 0-0 | 78-36-11 | D05638J | DED | | D08116P | DED | | | 280-299 | |
| 186 | 22 | | PA | 13-2 | SPARE | D05316P | CAP | Y | | D05668P | 22 | | | 050-099, 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 187 | 20 | PA | | | 13-2 | SPARE | D05316P | CAP | Y | | D05668P | 27 | | | 050-099, 150-199 |
| 188 | 24 | PK | | | 30-10 | 32-09-13 | D05638J | | 6 | | D05668P | 6 | | | ALL |
| 189 | 24 | PK | | | 15-0 | 24-51-71 | D05416P | | 22 | | D06260P | 21 | | | ALL |
| 190 | 24 | PK | | | 15-0 | 24-51-71 | D05416P | | 23 | | D06260P | 22 | | | ALL |
| 191 | 22 | PA | | | 25-2 | 21-51-21 | D08032P | | 54 | | D05668P | 35 | | | ALL |
| 192 | 24 | PK | | | 25-2 | 30-31-21 | D08032P | | 51 | | D05668P | 36 | | | ALL |
| 194 | 24 | PK | | | 25-2 | 21-53-21 | D08032P | | 46 | | D05668P | 34 | | | ALL |
| 195 | 24 | PK | | | 25-2 | 30-34-21 | D08032P | | 52 | | D05668P | 5 | | | ALL |
| 196 | 24 | PK | | | 20-8 | 32-09-12 | D05316P | | 54 | | D05638J | 17 | | | ALL |
| 197 | 24 | PK | | | 20-8 | 32-09-12 | D05316P | | 56 | | D05638J | 18 | | | ALL |
| 198 | 24 | PK | | | 20-8 | 32-09-12 | D05316P | | 57 | | D05638J | 19 | | | ALL |
| 199 | 24 | PK | | | 20-8 | 32-09-12 | D05316P | | 4 | | D05638J | 20 | | | ALL |
| 201B | 24 | PW | S | | 67-3 | 73-21-13 | D04624J | | 15 | | D05966J | 11 | | | 050-099 |
| 201B | 24 | PW | S | | 77-4 | 73-21-13 | D04624J | | 15 | | D05966J | 11 | | | 150-199 |
| 201B | 24 | PW | IA | | 77-4 | 73-21-13 | D04624J | | 15 | | D05966J | 11 | | | 275-299 |
| 201R | 24 | PW | S | | 0-0 | 73-21-13 | D04624J | | 16 | | D05966J | 12 | | | 050-099, 150-199 |
| 201R | 24 | PW | IA | | 0-0 | 73-21-13 | D04624J | | 16 | | D05966J | 12 | | | 275-299 |
| 201Z | | | S | | 0-0 | 73-21-13 | D04624J | = CC | D | | D05966J | | | FX | 050-099, 150-199 |
| 201Z | | | IA | | 0-0 | 73-21-13 | D04624J | = CC | L | | D05966J | | | FX | 275-276 |
| 201Z | | | IA | | 0-0 | 73-21-13 | D04624J | = CC | D | | D05966J | | | FX | 277-278 |
| 201Z | | | IA | | 0-0 | 73-21-13 | D04624J | = CC | M | | D05966J | | | FX | 280-299 |
| 202B | 24 | PW | W | | 18-0 | 73-21-14 | D05316P | | 47 | | D05622J | 38 | | | 050-099 |
| 202B | 24 | PW | T | | 18-0 | 73-21-14 | D05316P | | 47 | | D05622J | 38 | | | 150-199, 275-278 |
| 202B | 24 | PW | IB | | 18-0 | 73-21-14 | D05316P | | 47 | | D05622J | 38 | | | 280-299 |
| 202R | 24 | PW | W | | 0-0 | 73-21-14 | D05316P | | 26 | | D05622J | 39 | | | 050-099 |
| 202R | 24 | PW | T | | 0-0 | 73-21-14 | D05316P | | 26 | | D05622J | 39 | | | 150-199, 275-278 |
| 202R | 24 | PW | IB | | 0-0 | 73-21-14 | D05316P | | 26 | | D05622J | 39 | | | 280-299 |
| 202Z | | | W | | 0-0 | 73-21-14 | D05316P | | | FK | D05622J | | | FL | 050-099 |
| 202Z | | | T | | 0-0 | 73-21-14 | D05316P | | | FK | D05622J | | | FL | 150-199 |
| 202Z | | | T | | 0-0 | 73-21-14 | D05316P | | | FF | D05622J | | | FG | 275-278 |
| 202Z | | | IB | | 0-0 | 73-21-14 | D05316P | | | FF | D05622J | | | FG | 280-299 |
| 203B | 24 | PW | U | | 44-8 | 73-21-14 | D05622J | | 36 | | D04624J | 19 | | | 050-099 |
| 203B | 24 | PW | U | | 55-4 | 73-21-14 | D04624J | | 19 | | D05622J | 36 | | | 150-199 |
| 203B | 24 | PW | IC | | 55-4 | 73-21-14 | D05622J | | 36 | | D04624J | 19 | | | 275-299 |
| 203R | 24 | PW | U | | 0-0 | 73-21-14 | D04624J | | 20 | | D05622J | 37 | | | 050-099, 150-199 |
| 203R | 24 | PW | IC | | 0-0 | 73-21-14 | D05622J | | 37 | | D04624J | 20 | | | 275-299 |
| 203Z | | | U | | 0-0 | 73-21-14 | D04624J | = CC | D | | D05622J | | | FL | 050-099, 150-199 |
| 203Z | | | IC | | 0-0 | 73-21-14 | D05622J | | | FG | D04624J | = CC | D | | 275-278 |
| 203Z | | | IC | | 0-0 | 73-21-14 | D05622J | | | FG | D04624J | = CC | M | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 17

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|----|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | | |
| 204B | 24 | PW | V | | 18-0 | 73-21-14 | D05316P | | 46 | | | | D05622J | | 43 | | | 050-099, 150-199 |
| 204B | 24 | PW | ID | | 18-0 | 73-21-14 | D05316P | | 46 | | | | D05622J | | 43 | | | 275-299 |
| 204R | 24 | PW | V | | 0-0 | 73-21-14 | D05316P | | 39 | | | | D05622J | | 44 | | | 050-099, 150-199 |
| 204R | 24 | PW | ID | | 0-0 | 73-21-14 | D05316P | | 39 | | | | D05622J | | 44 | | | 275-299 |
| 204Z | | | V | | 0-0 | 73-21-14 | D05316P | | | | | | D05622J | | 45 | | | 050-099, 150-199 |
| 204Z | | | ID | | 0-0 | 73-21-14 | D05316P | | | | | | D05622J | | 45 | | | 275-299 |
| 205B | 24 | PW | IE | | 49-1 | 73-21-14 | D05316P | | 32 | | | | D04624J | | 23 | | | 050-099 |
| 205B | 24 | PW | W | | 59-9 | 73-21-14 | D04624J | | 23 | | | | D05316P | | 32 | | | 150-199 |
| 205B | 24 | PW | IE | | 59-9 | 73-21-14 | D05316P | | 32 | | | | D04624J | | 23 | | | 275-299 |
| 205R | 24 | PW | IE | | 0-0 | 73-21-14 | D05316P | | 53 | | | | D04624J | | 24 | | | 050-099, 275-299 |
| 205R | 24 | PW | W | | 0-0 | 73-21-14 | D04624J | | 24 | | | | D05316P | | 53 | | | 150-199 |
| 205Z | | | IE | | 0-0 | 73-21-14 | D05316P | | | | | | D04624J | = CC | D | | | 050-099 |
| 205Z | | | W | | 0-0 | 73-21-14 | D04624J | = CC | D | | | | D05316P | | | | FK | 150-199 |
| 205Z | | | IE | | 0-0 | 73-21-14 | D05316P | | | | | | D04624J | = CC | D | | | 275-278 |
| 205Z | | | IE | | 0-0 | 73-21-14 | D05316P | | | | | | D04624J | = CC | M | | | 280-299 |
| 206B | 24 | PL | C | | 18-0 | 27-81-21 | D05316P | | 12 | | | | D05622J | | 10 | | | 050-099, 150-199, 275-278 |
| 206B | 24 | PL | IF | | 18-0 | 27-81-21 | D05316P | | 12 | | | | D05622J | | 10 | | | 280-299 |
| 206R | 24 | PL | C | | 0-0 | 27-81-21 | D05316P | | 13 | | | | D05622J | | 11 | | | 050-099, 150-199, 275-278 |
| 206R | 24 | PL | IF | | 0-0 | 27-81-21 | D05316P | | 13 | | | | D05622J | | 11 | | | 280-299 |
| 207B | 22 | PB | AD | | 83-0 | 27-51-41 | D05316P | | 17 | | | | D01548 | | 1 | | | 050-099 |
| 207B | 22 | PB | AD | | 93-3 | 27-51-41 | D05316P | | 17 | | | | D01548 | | 1 | | | 150-199, 275-278 |
| 207B | 22 | PB | IG | | 93-3 | 27-51-41 | D05316P | | 17 | | | | D01548 | | 1 | | | 280-299 |
| 207R | 22 | PB | AD | | 0-0 | 27-51-41 | D05316P | | 18 | | | | D01548 | | 2 | | | 050-099, 150-199, 275-278 |
| 207R | 22 | PB | IG | | 0-0 | 27-51-41 | D05316P | | 18 | | | | D01548 | | 2 | | | 280-299 |
| 208B | 22 | PB | AB | | 85-1 | 27-58-21 | D08032P | | 20 | | | | D01548 | | 9 | | | 050-099 |
| 208B | 22 | PB | AB | | 95-4 | 27-58-21 | D08032P | | 20 | | | | D01548 | | 9 | | | 150-199, 275-276 |
| 208B | 22 | PB | IH | | 95-4 | 27-58-21 | D08032P | | 20 | | | | D01548 | | 9 | | | 277-299 |
| 208R | 22 | PB | AB | | 0-0 | 27-58-21 | D08032P | | 21 | | | | D01548 | | 8 | | | 050-099, 150-199, 275-276 |
| 208R | 22 | PB | IH | | 0-0 | 27-58-21 | D08032P | | 21 | | | | D01548 | | 8 | | | 277-299 |
| 209B | 24 | PL | Y | | 20-1 | 27-51-11 | D05622J | | 25 | | | | D08032P | | 25 | | | ALL |
| 209R | 24 | PL | Y | | 0-0 | 27-51-11 | D05622J | | 26 | | | | D08032P | | 26 | | | ALL |
| 211B | 24 | PL | Z | | 44-9 | 27-81-11 | D05622J | | 28 | | | | D05712J | | 4 | | | 050-099 |
| 211B | 24 | PL | Z | | 55-3 | 27-81-11 | D05622J | | 28 | | | | D05712J | | 4 | | | 150-199, 275-299 |
| 211R | 24 | PL | Z | | 0-0 | 27-81-11 | D05622J | | 29 | | | | D05712J | | 5 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0760
Page 18
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 217B | 24 | PW | IQ | 6-4 | 77-31-11 | D06140J | | 22 | | SM00039 | | VL | | 050-099, 150-199, 280-299 | |
| 217B | 24 | PW | JQ | 6-4 | 77-31-11 | D06140J | | 22 | | SM00039 | | VL | | 275-278 | |
| 217R | 24 | PW | IQ | 0-0 | 77-31-11 | D06140J | | 21 | | SM00040 | | VL | | 050-099, 150-199, 280-299 | |
| 217R | 24 | PW | JQ | 0-0 | 77-31-11 | D06140J | | 21 | | SM00040 | | VL | | 275-278 | |
| 217Z | | | IQ | 0-0 | 77-31-11 | D06140J | | 23 | | SM00039 | REF | | S1 | 050-099, 150-199, 280-299 | |
| 217Z | | | JQ | 0-0 | 77-31-11 | D06140J | | 23 | | SM00039 | REF | | S1 | 275-278 | |
| 218B | 24 | PW | IR | 14-1 | 77-31-11 | D06140J | | 19 | | D06278J | 11 | | | 050-099, 275-299 | |
| 218B | 24 | PW | AL | 14-1 | 77-31-11 | D06140J | | 19 | | D06278J | 11 | | | 150-199 | |
| 218R | 24 | PW | IR | 0-0 | 77-31-11 | D06140J | | 18 | | D06278J | 10 | | | 050-099, 275-299 | |
| 218R | 24 | PW | AL | 0-0 | 77-31-11 | D06140J | | 18 | | D06278J | 10 | | | 150-199 | |
| 218Z | | | IR | 0-0 | 77-31-11 | D06140J | | 20 | | D06278J | 12 | | | 050-099, 275-299 | |
| 218Z | | | AL | 0-0 | 77-31-11 | D06140J | | 20 | | D06278J | 12 | | | 150-199 | |
| 220R | 20 | RJ | AN | 14-1 | 77-31-11 | D05622J | | 33 | | D05638J | 10 | | | ALL | |
| 220W | 20 | RJ | AN | 0-0 | 77-31-11 | D05622J | | 34 | | D05638J | 11 | | | ALL | |
| 220Z | | | AN | 0-0 | 77-31-11 | D05622J | | 35 | | D05638J | 12 | | | ALL | |
| 223B | 24 | PW | BD | 51-8 | 77-12-12 | D08032P | | 50 | | D04624J | 39 | | | 050-099 | |
| 223B | 24 | PW | AO | 61-10 | 77-12-12 | D08032P | | 50 | | D04624J | 39 | | | 150-199 | |
| 223B | 24 | PW | BD | 61-10 | 77-12-12 | D08032P | | 50 | | D04624J | 39 | | | 275-276 | |
| 223B | 24 | PW | IW | 61-10 | 77-12-12 | D08032P | | 50 | | D04624J | 39 | | | 277-299 | |
| 223R | 24 | PW | BD | 0-0 | 77-12-12 | D08032P | | 47 | | D04624J | 36 | | | 050-099, 275-276 | |
| 223R | 24 | PW | AO | 0-0 | 77-12-12 | D08032P | | 47 | | D04624J | 36 | | | 150-199 | |
| 223R | 24 | PW | IW | 0-0 | 77-12-12 | D08032P | | 47 | | D04624J | 36 | | | 277-299 | |
| 223Z | | | BD | 0-0 | 77-12-12 | D08032P | | 49 | | D04624J | =CC | D | | 050-099 | |
| 223Z | | | AO | 0-0 | 77-12-12 | D08032P | | 49 | | D04624J | =CC | D | | 150-199 | |
| 223Z | | | BD | 0-0 | 77-12-12 | D08032P | | 49 | | D04624J | =CC | L | | 275-276 | |
| 223Z | | | IW | 0-0 | 77-12-12 | D08032P | | 49 | | D04624J | =CC | D | | 277-278 | |
| 223Z | | | IW | 0-0 | 77-12-12 | D08032P | | 49 | | D04624J | =CC | M | | 280-299 | |
| 225B | 20 | PR | F | 51-8 | 73-21-17 | D08032P | | 7 | | D04624J | 10 | | | 050-099 | |
| 225B | 24 | PW | IY | 61-10 | 73-21-17 | D08032P | | 7 | | D04624J | 10 | | | 150-199 | |
| 225B | 20 | PR | IY | 61-10 | 73-21-17 | D08032P | | 7 | | D04624J | 10 | | | 275-299 | |
| 225R | 20 | PR | F | 0-0 | 73-21-12 | D08032P | | 16 | | D04624J | 12 | | | 050-099 | |
| 225R | 24 | PW | IY | 0-0 | 73-21-12 | D08032P | | 16 | | D04624J | 12 | | | 150-199 | |
| 225R | 20 | PR | IY | 0-0 | 73-21-12 | D08032P | | 16 | | D04624J | 12 | | | 275-299 | |
| 225Z | | | F | 0-0 | 73-21-12 | D08032P | | | FI | D04624J | =CC | D | | 050-099 | |
| 225Z | | | IY | 0-0 | 73-21-17 | D08032P | | | FD | D04624J | =CC | M | | 150-156, 162-166 | |
| 225Z | | | IY | 0-0 | 73-21-17 | D08032P | | | FD | D04624J | =CC | D | | 157, 167-199 | |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 19

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| 225Z | | | | IY | 0-0 | 73-21-12 | D08032P | | | FI | D04624J | =CC | L | | 275-276 |
| 225Z | | | | IY | 0-0 | 73-21-12 | D08032P | | | FI | D04624J | =CC | D | | 277-278 |
| 225Z | | | | IY | 0-0 | 73-21-12 | D08032P | | | FI | D04624J | =CC | M | | 280-299 |
| 227B | 24 | | PW | JB | 20-7 | 77-12-11 | D06260P | 15 | | | D05638J | 22 | | | 050-099 |
| 227B | 24 | | PW | JB | 20-7 | 77-12-11 | D05638J | 22 | | | D06260P | 15 | | | 150-199, 275-299 |
| 227R | 24 | | PW | JB | 0-0 | 77-12-11 | D06260P | 28 | | | D05638J | 21 | | | 050-099 |
| 227R | 24 | | PW | JB | 0-0 | 77-12-11 | D05638J | 21 | | | D06260P | 28 | | | 150-199, 275-299 |
| 227Z | | | | JB | 0-0 | 77-12-11 | D06260P | 32 | | | D05638J | 23 | | | 050-099 |
| 227Z | | | | JB | 0-0 | 77-12-11 | D05638J | 23 | | | D06260P | 32 | | | 150-199, 275-299 |
| 235 | 24 | | PV | B | 7-1 | 73-21-11 | D06260P | 10 | | | SM00027 | | S | | 150-157 |
| 235 | 24 | | PV | JI | 7-1 | 73-21-11 | D06260P | 10 | | | SM00027 | | S | | 275 |
| 235Z | | | | B | 0-0 | 73-21-11 | D06260P | | | FH | SM00027 | REF | | FJ | 150-157 |
| 235Z | | | | JI | 0-0 | 73-21-11 | D06260P | | | AS | SM00027 | REF | V | | 275 |
| 239B | 24 | | PW | JN | 14-5 | 77-12-12 | D08032P | 14 | | | SM00039 | | VL | | 050-099, 275-299 |
| 239B | 24 | | PW | AA | 14-5 | 77-12-12 | D08032P | 14 | | | SM00039 | | VL | | 150-199 |
| 239R | 24 | | PW | JN | 0-0 | 77-12-12 | D08032P | 13 | | | SM00040 | | VL | | 050-099, 275-299 |
| 239R | 24 | | PW | AA | 0-0 | 77-12-12 | D08032P | 13 | | | SM00040 | | VL | | 150-199 |
| 239Z | | | | JN | 0-0 | 77-12-12 | D08032P | 15 | | | SM00039 | REF | | S1 | 050-099, 275-299 |
| 239Z | | | | AA | 0-0 | 77-12-12 | D08032P | 15 | | | SM00039 | REF | | S1 | 150-199 |
| 243B | 24 | | PW | JR | 9-4 | 77-12-12 | D05638J | 13 | | | SM00039 | | VL | | 050-099, 275-299 |
| 243B | 24 | | PW | AG | 9-4 | 77-12-12 | SM00039 | | VL | | D05638J | 13 | | | 150-199 |
| 243R | 24 | | PW | JR | 0-0 | 77-12-12 | D05638J | 14 | | | SM00040 | | VL | | 050-099, 275-299 |
| 243R | 24 | | PW | AG | 0-0 | 77-12-12 | SM00040 | | VL | | D05638J | 14 | | | 150-199 |
| 243Z | | | | JR | 0-0 | 77-12-12 | D05638J | 15 | | | SM00039 | REF | | S1 | 050-099, 275-299 |
| 243Z | | | | AG | 0-0 | 77-12-12 | SM00039 | REF | | S1 | D05638J | 15 | | | 150-199 |
| 251B | 24 | | PW | KA | 17-7 | 73-21-14 | D06140J | 12 | | | D06260P | 24 | | | 050-099 |
| 251B | 24 | | PW | AJ | 17-7 | 73-21-14 | D06260P | 24 | | | D06140J | 12 | | | 150-199 |
| 251B | 24 | | PW | KA | 17-7 | 73-21-14 | D06260P | 24 | | | D06140J | 12 | | | 275-299 |
| 251R | 24 | | PW | KA | 0-0 | 73-21-14 | D06140J | 13 | | | D06260P | 25 | | | 050-099 |
| 251R | 24 | | PW | AJ | 0-0 | 73-21-14 | D06260P | 25 | | | D06140J | 13 | | | 150-199 |
| 251R | 24 | | PW | KA | 0-0 | 73-21-14 | D06260P | 25 | | | D06140J | 13 | | | 275-299 |
| 251Z | | | | KA | 0-0 | 73-21-14 | D06140J | 14 | | | D06260P | 26 | | | 050-099 |
| 251Z | | | | AJ | 0-0 | 73-21-14 | D06260P | 26 | | | D06140J | 14 | | | 150-199 |
| 251Z | | | | KA | 0-0 | 73-21-14 | D06260P | 26 | | | D06140J | 14 | | | 275-299 |
| 294B | 24 | | PW | LS | 63-0 | 31-35-15 | D04667J | 34 | | | D04624J | 30 | | | 277 |
| 294R | 24 | | PW | LS | 0-0 | 31-35-15 | D04667J | 33 | | | D04624J | 31 | | | 277 |
| 294Z | | | | LS | 0-0 | 31-35-15 | D04667J | | | FS | D04624J | | | FT | 277 |
| 302B | 24 | | PX | X | 67-3 | 73-21-13 | D04624J | 27 | | | D05966J | 7 | | | 050-099 |
| 302B | 24 | | PX | X | 77-4 | 73-21-13 | D04624J | 27 | | | D05966J | 7 | | | 150-199, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 20

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | |
| 302B | 24 | PX | MB | 77-4 | 73-21-13 | D04624J | 27 | | | | D05966J | 7 | | | 277-299 | |
| 302R | 24 | PX | X | 0-0 | 73-21-13 | D04624J | 26 | | | | D05966J | 6 | | | 050-099, 150-199, 275-276 | |
| 302R | 24 | PX | MB | 0-0 | 73-21-13 | D04624J | 26 | | | | D05966J | 6 | | | 277-299 | |
| 302Y | 24 | PX | X | 0-0 | 73-21-13 | D04624J | 25 | | | | D05966J | 8 | | | 050-099, 150-199, 275-276 | |
| 302Y | 24 | PX | MB | 0-0 | 73-21-13 | D04624J | 25 | | | | D05966J | 8 | | | 277-299 | |
| 302Z | | | X | 0-0 | 73-21-13 | D04624J | = CC | D | | | D05966J | | | FY | 050-099, 150-199, 275-276 | |
| 302Z | | | MB | 0-0 | 73-21-13 | D04624J | = CC | D | | | D05966J | | | FY | 277-278 | |
| 302Z | | | MB | 0-0 | 73-21-13 | D04624J | = CC | M | | | D05966J | | | FY | 280-299 | |
| 303B | 24 | PM | D | 18-0 | 27-81-21 | D05316P | 14 | | | | D05622J | 12 | | | 050-099, 275-278 | |
| 303B | 24 | PM | MC | 18-0 | 27-81-21 | D05316P | 14 | | | | D05622J | 12 | | | 150-199, 280-299 | |
| 303R | 24 | PM | D | 0-0 | 27-81-21 | D05316P | 15 | | | | D05622J | 13 | | | 050-099, 275-278 | |
| 303R | 24 | PM | MC | 0-0 | 27-81-21 | D05316P | 15 | | | | D05622J | 13 | | | 150-199, 280-299 | |
| 303Y | 24 | PM | D | 0-0 | 27-81-21 | D05316P | 16 | | | | D05622J | 14 | | | 050-099, 275-278 | |
| 303Y | 24 | PM | MC | 0-0 | 27-81-21 | D05316P | 16 | | | | D05622J | 14 | | | 150-199, 280-299 | |
| 304B | 22 | PC | MD | 85-1 | 27-58-21 | D08032P | 22 | | | | D01548 | 12 | | | 050-099 | |
| 304B | 22 | PC | AC | 95-4 | 27-58-21 | D08032P | 22 | | | | D01548 | 12 | | | 150-199, 275-278 | |
| 304B | 22 | PC | MD | 95-4 | 27-58-21 | D08032P | 22 | | | | D01548 | 12 | | | 280-299 | |
| 304R | 22 | PC | MD | 0-0 | 27-58-21 | D08032P | 23 | | | | D01548 | 10 | | | 050-099, 280-299 | |
| 304R | 22 | PC | AC | 0-0 | 27-58-21 | D08032P | 23 | | | | D01548 | 10 | | | 150-199, 275-278 | |
| 304Y | 22 | PC | MD | 0-0 | 27-58-21 | D08032P | 24 | | | | D01548 | 11 | | | 050-099, 280-299 | |
| 304Y | 22 | PC | AC | 0-0 | 27-58-21 | D08032P | 24 | | | | D01548 | 11 | | | 150-199, 275-278 | |
| 306B | 24 | PM | MF | 44-9 | 27-81-11 | D05622J | 30 | | | | D05712J | 6 | | | 050-099 | |
| 306B | 24 | PM | AP | 55-3 | 27-81-11 | D05622J | 30 | | | | D05712J | 6 | | | 150-199 | |
| 306B | 24 | PM | MF | 55-3 | 27-81-11 | D05622J | 30 | | | | D05712J | 6 | | | 275-299 | |
| 306R | 24 | PM | MF | 0-0 | 27-81-11 | D05622J | 31 | | | | D05712J | 7 | | | 050-099, 275-299 | |
| 306R | 24 | PM | AP | 0-0 | 27-81-11 | D05622J | 31 | | | | D05712J | 7 | | | 150-199 | |
| 306Y | 24 | PM | MF | 0-0 | 27-81-11 | D05622J | 32 | | | | D05712J | 8 | | | 050-099, 275-299 | |
| 306Y | 24 | PM | AP | 0-0 | 27-81-11 | D05622J | 32 | | | | D05712J | 8 | | | 150-199 | |
| 401B | 22 | PD | AE | 83-0 | 27-51-41 | D05316P | 19 | | | | D01548 | 3 | | | 050-099 | |
| 401B | 22 | PD | AE | 93-3 | 27-51-41 | D05316P | 19 | | | | D01548 | 3 | | | 150-199, 275-299 | |
| 401G | 22 | PD | AE | 0-0 | 27-51-41 | D05316P | 20 | | | | D01548 | 6 | | | ALL | |
| 401R | 22 | PD | AE | 0-0 | 27-51-41 | D05316P | 21 | | | | D01548 | 4 | | | ALL | |
| 401Y | 22 | PD | AE | 0-0 | 27-51-41 | D05316P | 22 | | | | D01548 | 5 | | | ALL | |
| 500 | 18 | PA | | 24-7 | 78-34-21 | D01404 | | CAP | Y | | D04758P | | CAP | Y | 050-099 | |
| 500 | 18 | PA | | 24-7 | 78-34-21 | D04758P | | CAP | Y | | D01404 | | CAP | Y | 150-156, 162-166, 275-276 | |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 21

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | |
| 500 | 18 | PA | | 24-7 | SPARE | | D04758P | | CAP | Y | | D01404 | | CAP | Y | 157, 167-199, 277-299 |
| 501 | 22 | PA | | 20-8 | SPARE | | D05316P | | CAP | Y | | D05638J | | 5 | | 150-199 |
| 502 | 22 | PA | | 20-8 | SPARE | | D05316P | | CAP | Y | | D05638J | | CAP | Y | 150-199 |
| 503 | 22 | PA | | 20-8 | SPARE | | D05316P | | CAP | Y | | D05638J | | 8 | | 050-099, 150-199 |
| 507 | 20 | PA | | 1-3 | | 24-22-11 | D01404 | | | 8 | | GD03816 | | D.. | E | 050-099, 277-299 |
| 507 | 20 | PA | | 1-3 | | 24-22-11 | D01404 | | | 8 | | GD03814 | | D.. | E | 150-199, 275-276 |
| 508 | 24 | PK | | 28-11 | | 24-22-11 | D01404 | | | 7 | | SP02494 | | | 9 | ALL |
| 509 | 12 | PA | | 15-4 | | 28-22-12 | D06258P | | | 1 | | D06260P | | | 1 | ALL |
| 510 | 12 | PA | | 15-4 | | 28-22-12 | D06258P | | | 2 | | D06260P | | | 2 | ALL |
| 511 | 12 | PA | | 15-4 | | 28-22-12 | D06258P | | | 4 | | D06260P | | | 4 | ALL |
| 512 | 24 | PK | | 12-4 | | 21-31-21 | D05622J | | | 52 | | SP02562 | | | | S |
| 513 | 24 | PK | | 28-11 | | 21-31-11 | D01404 | | | 11 | | SP02562 | | | | S |
| 514 | 24 | PK | | 25-9 | SPARE | | D01404 | | | 13 | | D06260P | | CAP | Y | 150-199 |
| 515 | 24 | PK | | 25-9 | SPARE | | D01404 | | | 14 | | D06260P | | CAP | Y | 150-199 |
| 517 | 24 | PK | | 19-9 | | 27-51-11 | D06140J | | | 11 | | D08032P | | | 36 | ALL |
| 518 | 12 | PA | | 28-2 | | 24-51-24 | D06260P | | | 6 | | SP02756 | | | 9 | ALL |
| 534 | 18 | PA | | 24-7 | | 78-34-21 | D01404 | | CAP | Y | | D04758P | | CAP | Y | 050-099 |
| 534 | 18 | PA | | 24-7 | | 78-34-21 | D04758P | | CAP | Y | | D01404 | | CAP | Y | 150-156, 162-166, 275-276 |
| 534 | 18 | PA | | 24-7 | SPARE | | D04758P | | CAP | Y | | D01404 | | CAP | Y | 157, 167-199, 277-299 |
| 535 | 18 | PA | | 2-5 | | 78-34-21 | D01404 | | | 22 | DK | GD00561 | | D.. | 2 | 050-099 |
| 535 | 18 | PA | | 1-3 | | 78-34-21 | GD03816 | | | D.. | E | D01404 | | | 22 | DK |
| 535 | 18 | PA | | 2-5 | | 78-34-21 | GD00561 | | | D.. | 2 | D01404 | | | 22 | DK |
| 544 | 24 | PK | | 49-1 | | 24-11-21 | D06588J | | | 2 | | D05316P | | | 51 | 050-099 |
| 544 | 24 | PK | | 59-9 | | 24-11-21 | D05316P | | | 51 | | D06588J | | | 2 | 150-199, 275-299 |
| 547 | 24 | PV | VV | 44-8 | | 73-21-17 | D05622J | | | 48 | | D04624J | | | 1 | 050-099 |
| 547 | 24 | PV | VV | 55-4 | | 73-21-17 | D05622J | | | 48 | | D04624J | | | 1 | 150-199 |
| 547 | 24 | PV | VV | 55-4 | | 73-21-17 | D04624J | | | 1 | | D05622J | | | 48 | 275-299 |
| 547Z | | | VV | 0-0 | | 73-21-17 | D05622J | | | | VV | D04624J | | =CC | D | 050-099, 150-199 |
| 547Z | | | VV | 0-0 | | 73-21-17 | D04624J | | =CC | L | | D05622J | | | | FJ |
| 547Z | | | VV | 0-0 | | 73-21-17 | D04624J | | =CC | D | | D05622J | | | | FJ |
| 547Z | | | VV | 0-0 | | 73-21-17 | D04624J | | =CC | M | | D05622J | | | | FJ |
| 548 | 24 | PV | VW | 20-1 | | 73-21-17 | D08032P | | | 55 | | D05622J | | | 47 | 050-099, 275-299 |
| 548 | 24 | PV | VW | 20-1 | | 73-21-17 | D05622J | | | 47 | | D08032P | | | 55 | 150-199 |
| 548Z | | | VW | 0-0 | | 73-21-17 | D08032P | | | 56 | | D05622J | | | | VV |
| 548Z | | | VW | 0-0 | | 73-21-17 | D05622J | | | | VV | D08032P | | | 56 | 150-199 |
| 548Z | | | VW | 0-0 | | 73-21-17 | D08032P | | | 56 | | D05622J | | | | FJ |
| 589 | 24 | PK | | 25-5 | SPARE | | D04758P | | | 38 | | D05668P | | | 38 | 150-154 |
| 589 | 24 | PK | | 25-5 | | 73-21-16 | D04758P | | | 38 | | D05668P | | | 38 | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 22

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | | | |
| 598 | 24 | | PK | 25-5 | 73-21-16 | D04758P | | 38 | | | | | D05668P | 38 | | | 050-099 |
| 598 | 24 | | PK | 25-5 | SPARE | D04758P | | 38 | | | | | D05668P | 38 | | | 155-199 |
| 609 | 24 | | PV | YI | 25-2 | 73-21-14 | D05668P | | 31 | | | | D08032P | 11 | | | 050-099, 150-199 |
| 609 | 24 | | PV | YI | 25-2 | 73-21-14 | D08032P | | 11 | | | | D05668P | 31 | | | 275-299 |
| 609Z | | | | YI | 0-0 | 73-21-14 | D05668P | | 32 | | | | D08032P | | | FI | 050-099 |
| 609Z | | | | YI | 0-0 | 73-21-14 | D05668P | | 32 | | | | D08032P | | | FD | 150-199 |
| 609Z | | | | YI | 0-0 | 73-21-14 | D08032P | | | | | FI | D05668P | 32 | | | 275-299 |
| 610 | 18 | | PQ | YJ | 50-0 | 78-34-21 | D20162 | | 5 | DK | | | D06260P | 19 | DL | | ALL |
| 610Z | | | | YJ | 0-0 | 78-34-21 | D20162 | | | | | FR | D06260P | 20 | | | ALL |
| 611 | 18 | | PQ | YK | 60-0 | 78-34-21 | D20162 | | 8 | DK | | | D05668P | 33 | DK | | ALL |
| 611Z | | | | YK | 0-0 | 78-34-21 | D20162 | | | | | FR | D05668P | | | FQ | ALL |
| 612 | 20 | | UA | | 3-0 | 78-34-21 | D20162 | | | | | FR | GD00649 | S.. | 2 | | ALL |
| 817 | 22 | | PA | | 21-11 | 73-21-19 | D08032P | | 45 | | | | D08018P | 5 | | | 050-099 |
| 817 | 22 | | PA | | 21-11 | 73-21-19 | D08018P | | 5 | | | | D08032P | 45 | | | 150-199, 275-299 |
| FR2 | | | | | 0-0 | 73-21-13 | D05966J | | | | | FX | GD00561 | S.. | 2 | | 157, 167-199, 277-299 |
| FR3 | | | | | 0-0 | 73-21-13 | D05966J | | | | | FY | GD00561 | S.. | 2 | | 157, 167-199, 277-299 |
| FRA | | | | | 0-0 | 78-34-21 | D04758P | | | | | FA | D04758P | 16 | | | ALL |
| FRC | | | | | 0-0 | 73-21-11 | D08032P | | 39 | | | | D08032P | | | FC | 275-299 |
| FRD | | | | | 2-0 | 73-21-17 | D08032P | | 28 | | | | D08032P | | | FD | 150-199 |
| FRF | | | | | 0-0 | 73-21-11 | D06258P | | | | | FF | D06258P | 16 | | | 050-099 |
| FRF | | | | | 2-0 | 73-21-11 | D06258P | | 16 | | | | D06258P | | | FF | 150-199 |
| FRF | | | | | 0-0 | 73-21-14 | D05316P | | 24 | | | | D05316P | | | FF | 275-299 |
| FRG | | | | | 0-0 | 73-21-14 | D05622J | | | | | FG | D05622J | 40 | | | 275-299 |
| FRH | | | | | 0-0 | 73-21-11 | D06260P | | 29 | | | | D06260P | | | FH | 050-099 |
| FRH | | | | | 2-0 | 73-21-11 | D06260P | | | | | FH | D06260P | 29 | | | 150-199 |
| FRH | | | | | 0-0 | 73-21-11 | D06258P | | | | | FH | D06258P | 16 | | | 275-299 |
| FRI | | | | | 0-0 | 73-21-17 | D08032P | | | | | FI | D08032P | 28 | | | 050-099, 275-299 |
| FRJ | | | | | 0-0 | 73-21-17 | D05622J | | 46 | | | | D05622J | | | FJ | 275-299 |
| FRK | | | | | 0-0 | 73-21-14 | D05316P | | | | | FK | D05316P | 24 | | | 050-099 |
| FRK | | | | | 2-0 | 73-21-14 | D05316P | | 24 | | | | D05316P | | | FK | 150-199 |
| FRK | | | | | 0-0 | 73-21-11 | D06260P | | 29 | | | | D06260P | | | AS | 275-299 |
| FRL | | | | | 0-0 | 73-21-14 | D05622J | | | | | FL | D05622J | 40 | | | 050-099 |
| FRL | | | | | 2-0 | 73-21-14 | D05622J | | 40 | | | | D05622J | | | FL | 150-199 |
| FRM | | | | | 0-0 | 73-21-11 | D08032P | | 39 | | | | D08032P | | | FM | 050-099 |
| FRM | | | | | 2-0 | 73-21-11 | D08032P | | 39 | | | | D08032P | | | FM | 150-199 |
| FRQ | | | | | 0-0 | 78-34-21 | D05668P | | 39 | | | | D05668P | | | FQ | ALL |
| FRR | | | | | 0-0 | 78-34-21 | D20162 | | 4 | | | | D20162 | | | FR | ALL |
| FRS | | | | | 0-0 | 31-35-15 | D04667J | | 35 | | | | D04667J | | | FS | 277 |
| FRT | | | | | 0-0 | 31-35-15 | D04624J | | = CC | | | | D04624J | | | FT | 277 |

WIRE LIST

D280T132

91-21-11

Section W0760

Page 23

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0768 | 286T0768 | | | P61 TO R WING RS - R2A - FLT CONT & ENG INSTR (continued) | | | | | | | | | | | |
| FRU | | | | | 0-0 | 78-34-21 | D20162 | | 7 | | D20162 | | | FR | ALL |
| FRV | | | | | 2-0 | 73-21-17 | D05622J | | | VV | D05622J | | 46 | | 150-199 |
| FRX | | | | | 0-0 | 73-21-13 | D05966J | | | FX | D05966J | | 10 | | ALL |
| FRY | | | | | 0-0 | 73-21-13 | D05966J | | | FY | D05966J | | 1 | | ALL |
| FRZ | | | | | 0-0 | 73-21-17 | D05622J | | | VV | D05622J | | 46 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0760
Page 24 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0770 | 286T0770 | | | P37 TO TAIL-R2-FLT CONT | | | | | | | | | | | |
| 001 | 20 | PA | | | 128-0 | 27-23-11 | D05440P | | 1 | | D05318P | | 1 | | 050-099 |
| 001 | 20 | PA | | | 147-0 | 27-23-11 | D05440P | | 1 | | D05318P | | 1 | | 150-157, 275-299 |
| 001 | 20 | PA | | | 148-0 | 27-23-11 | D05440P | | 1 | | D05318P | | 1 | | 162-199 |
| 002 | 20 | PA | | | 128-0 | 27-23-11 | D05440P | | 2 | | D05318P | | 2 | | 050-099 |
| 002 | 20 | PA | | | 147-0 | 27-23-11 | D05440P | | 2 | | D05318P | | 2 | | 150-157, 275-299 |
| 002 | 20 | PA | | | 148-0 | 27-23-11 | D05440P | | 2 | | D05318P | | 2 | | 162-199 |
| 003 | 22 | PA | | | 128-0 | 27-23-11 | D05440P | | 3 | | D05318P | | 3 | | 050-099 |
| 003 | 22 | PA | | | 148-0 | 27-23-11 | D05440P | | 3 | | D05318P | | 3 | | 150-199, 275-278 |
| 003 | 22 | PA | | | 147-0 | 27-23-11 | D05440P | | 3 | | D05318P | | 3 | | 280-299 |
| 004 | 22 | PA | | | 147-0 | SPARE | D05440P | | 4 | | D05318P | | 4 | | 150-157, 275-299 |
| 004 | 22 | PA | | | 148-0 | SPARE | D05440P | CAP | Y | | D05318P | CAP | Y | | 162-199 |
| 005 | 22 | PA | | | 147-0 | SPARE | D05440P | | 5 | | D05318P | | 5 | | 150-157, 275-299 |
| 005 | 22 | PA | | | 148-0 | SPARE | D05440P | CAP | Y | | D05318P | CAP | Y | | 162-199 |
| 101 | 18 | PA | | | 7-0 | 21-66-21 | D13916 | | 8 | DK | GD01918 | A.. | 2 | | 050-099, 162-199 |
| 102 | 18 | PA | | | 7-0 | 21-66-21 | D13916 | | 7 | DK | GD01918 | S.. | 2 | | 050-099, 162-199 |
| 103 | 20 | PA | | | 7-0 | 21-66-21 | D13888 | | 4 | | GD01918 | S.. | 2 | | 050-099, 162-199 |
| 104 | 20 | PA | | | 37-0 | 21-66-21 | D13888 | | 1 | | D05318P | | 8 | | 050-099 |
| 104 | 20 | PA | | | 37-0 | 21-66-21 | D05318P | | 8 | | D13888 | | 1 | | 162-199 |
| 105 | 20 | PA | | | 37-0 | 21-66-21 | D13888 | | 2 | | D05318P | | 9 | | 050-099 |
| 105 | 20 | PA | | | 37-0 | 21-66-21 | D05318P | | 9 | | D13888 | | 2 | | 162-199 |
| 106 | 20 | PA | | | 5-0 | 21-66-21 | D13884 | | 3 | | GD01918 | S.. | 2 | | 050-099, 162-199 |
| 107 | 20 | PA | | | 27-0 | 21-66-41 | D13906 | | 4 | | GD01776 | S.. | 2 | | 050-099 |
| 107 | 20 | PA | | | 21-0 | 21-66-41 | D13906 | | 4 | | GD01774 | S.. | 2 | | 150, 152-199 |
| 108 | 20 | PA | | | 119-0 | 21-66-41 | D13906 | | 1 | | D05318P | | 16 | | 050-099 |
| 108 | 20 | PA | | | 140-0 | 21-66-41 | D13906 | | 1 | | D05318P | | 16 | | 150, 152-199 |
| 109 | 20 | PA | | | 119-0 | 21-66-41 | D13906 | | 2 | | D05318P | | 17 | | 050-099 |
| 109 | 20 | PA | | | 140-0 | 21-66-41 | D13906 | | 2 | | D05318P | | 17 | | 150, 152-199 |
| 110 | 20 | PA | | | 119-0 | 21-66-41 | D13906 | | 3 | | D05318P | | 15 | | 050-099 |
| 110 | 20 | PA | | | 140-0 | 21-66-41 | D13906 | | 3 | | D05318P | | 15 | | 150, 152-199 |
| 111 | 22 | PA | | | 120-0 | 21-66-41 | D13914 | | 32 | | D05318P | | 18 | | 050-099 |
| 111 | 22 | PA | | | 141-0 | 21-66-41 | D13914 | | 32 | | D05318P | | 18 | | 150, 152-199 |
| 112 | 22 | PA | | | 120-0 | 21-66-41 | D13914 | | 33 | | D05318P | | 19 | | 050-099 |
| 112 | 22 | PA | | | 141-0 | 21-66-41 | D13914 | | 33 | | D05318P | | 19 | | 150, 152-199 |
| 113 | 22 | PA | | | 120-0 | 21-66-41 | D13914 | | 29 | | D05318P | | 20 | | 050-099 |
| 113 | 22 | PA | | | 141-0 | 21-66-41 | D13914 | | 29 | | D05318P | | 20 | | 150, 152-199 |
| 114 | 22 | PA | | | 1-0 | 21-66-41 | D13914 | | 43 | | D13914 | | 48 | | 050-099, 150, 152-199 |
| 115 | 20 | PA | | | 37-0 | 21-66-21 | D13888 | | 3 | | D05318P | | 7 | | 050-099 |
| 115 | 20 | PA | | | 37-0 | 21-66-21 | D05318P | | 7 | | D13888 | | 3 | | 162-199 |
| 120 | 20 | PA | | | 28-0 | 21-66-41 | D13910 | | 8 | | GD01776 | A.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0770

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0770 | 286T0770 | | | P37 TO TAIL-R2-FLT CONT (continued) | | | | | | | | | | | | | |
| 120 | 20 | | PA | 22-0 | 21-66-41 | D13910 | | | 8 | | | | GD01774 | A.. | 2 | | 150, 152-199 |
| 121 | 20 | | PA | 22-0 | 21-66-41 | D13910 | | | 7 | | | | GD01774 | S.. | 2 | | 050-099, 150, 152-199 |
| 122 | 22 | | PA | 120-0 | 21-66-41 | D13914 | | | 31 | | | | D05318P | 11 | | | 050-099 |
| 122 | 22 | | PA | 141-0 | 21-66-41 | D05318P | | | 11 | | | | D13914 | 31 | | | 150, 152-199 |
| 123 | 22 | | PA | 120-0 | 21-66-41 | D13914 | | | 18 | | | | D05318P | 10 | | | 050-099 |
| 123 | 22 | | PA | 141-0 | 21-66-41 | D05318P | | | 10 | | | | D13914 | 18 | | | 150, 152-199 |
| 124 | 20 | | PA | 22-0 | 21-66-41 | D13914 | | | 13 | | | | GD01774 | D.. | 2 | | 050-099, 150, 152-199 |
| 125 | 22 | | PA | 2-0 | 21-66-41 | D13914 | | | 15 | | | | D13914 | 16 | | | 050-099, 150, 152-199 |
| 126 | 20 | | PA | 22-0 | 21-66-41 | D13914 | | | 60 | | | | GD01774 | S.. | 2 | | 050-099, 150, 152-199 |
| 127 | 20 | | PA | 22-0 | 21-66-41 | D13912 | | | 23 | | | | GD01774 | S.. | 2 | | 050-099, 150, 152-199 |
| 128 | 20 | | PA | 19-0 | 21-66-41 | D13904 | | | 3 | | | | GD01774 | S.. | 2 | | 050-099, 150, 152-199 |
| 201 | 20 | | UA | 22-0 | 21-66-41 | D13912 | | | | | | FD | GD01774 | S.. | 2 | | 050-099, 150, 152-199 |
| 201B | 22 | | PR IA | 120-0 | 21-66-41 | D13912 | | | 22 | | | | D05318P | 22 | | | 050-099 |
| 201B | 22 | | PR IA | 141-0 | 21-66-41 | D13912 | | | 22 | | | | D05318P | 22 | | | 150, 152-199 |
| 201R | 22 | | PR IA | 0-0 | 21-66-41 | D13912 | | | 21 | | | | D05318P | 21 | | | 050-099, 150, 152-199 |
| 201Z | | | IA | 0-0 | 21-66-41 | D13912 | | | | | | FD | D05318P | 23 | | | 050-099, 150, 152-199 |
| 202B | 22 | | PB IB | 4-0 | 21-66-41 | D13914 | | | 3 | | | | D13900 | 1 | | | 050-099, 150, 152-199 |
| 202R | 22 | | PB IB | 0-0 | 21-66-41 | D13914 | | | 4 | | | | D13900 | 3 | | | 050-099, 150, 152-199 |
| 203B | 22 | | PB IC | 16-0 | 21-66-41 | D13914 | | | 5 | | | | D13902 | 1 | | | 050-099, 150, 152-199 |
| 203R | 22 | | PB IC | 0-0 | 21-66-41 | D13914 | | | 6 | | | | D13902 | 2 | | | 050-099, 150, 152-199 |
| 300 | 20 | | UA | 22-0 | 21-66-41 | D13910 | | | | | | FB | GD01774 | S.. | 2 | | 050-099, 150, 152-199 |
| 300B | 18 | | PS EP | 5-0 | 21-66-41 | D13910 | | | 4 | DK | | | D13904 | 2 | DK | | 050-099, 150, 152-199 |
| 300R | 18 | | PS EP | 0-0 | 21-66-41 | D13910 | | | 5 | DK | | | D13904 | 4 | DK | | 050-099, 150, 152-199 |
| 300Y | 18 | | PS EP | 0-0 | 21-66-41 | D13910 | | | 6 | DK | | | D13904 | 1 | DK | | 050-099, 150, 152-199 |
| 300Z | | | EP | 0-0 | 21-66-41 | D13910 | | | | | | FB | D13904 | DED | | | 050-099, 150, 152-199 |
| 301B | 18 | | PC FA | 38-0 | 21-66-21 | D13916 | | | 11 | DK | | | D05318P | 6 | DK | | 050-099 |
| 301B | 18 | | PC FA | 38-0 | 21-66-21 | D05318P | | | 6 | DK | | | D13916 | 11 | DK | | 162-199 |
| 301R | 18 | | PC FA | 0-0 | 21-66-21 | D13916 | | | 9 | DK | | | D05318P | 4 | DK | | 050-099 |
| 301R | 18 | | PC FA | 0-0 | 21-66-21 | D05318P | | | 4 | DK | | | D13916 | 9 | DK | | 162-199 |
| 301Y | 18 | | PC FA | 0-0 | 21-66-21 | D13916 | | | 10 | DK | | | D05318P | 5 | DK | | 050-099 |
| 301Y | 18 | | PC FA | 0-0 | 21-66-21 | D05318P | | | 5 | DK | | | D13916 | 10 | DK | | 162-199 |
| 302 | 18 | | UA | 7-0 | 21-66-21 | D13916 | | | | | | FA | GD01918 | S.. | 2 | | 050-099, 162-199 |
| 302B | 18 | | PS FB | 5-0 | 21-66-21 | D13916 | | | 4 | DK | | | D13884 | 2 | DK | | 050-099, 162-199 |
| 302R | 18 | | PS FB | 0-0 | 21-66-21 | D13916 | | | 5 | DK | | | D13884 | 4 | DK | | 050-099, 162-199 |
| 302Y | 18 | | PS FB | 0-0 | 21-66-21 | D13916 | | | 6 | DK | | | D13884 | 1 | DK | | 050-099, 162-199 |
| 302Z | | | FB | 0-0 | 21-66-21 | D13916 | | | | | | FA | D13884 | DED | | | 050-099, 162-199 |
| 304B | 18 | | PC MB | 120-0 | 21-66-41 | D13910 | | | 11 | DK | | | D05318P | 14 | DK | | 050-099 |
| 304B | 18 | | PC MB | 141-0 | 21-66-41 | D05318P | | | 14 | DK | | | D13910 | 11 | DK | | 150, 152-199 |
| 304R | 18 | | PC MB | 0-0 | 21-66-41 | D13910 | | | 9 | DK | | | D05318P | 12 | DK | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0770

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|-----------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0770 | 286T0770 | | | P37 TO TAIL-R2-FLT CONT (continued) | | | | | | | | | | | | |
| 304R | 18 | PC | MB | 0-0 | 21-66-41 | D05318P | 12 | DK | | D13910 | 9 | DK | | 150, 152-199 | | |
| 304Y | 18 | PC | MB | 0-0 | 21-66-41 | D13910 | 10 | DK | | D05318P | 13 | DK | | 050-099 | | |
| 304Y | 18 | PC | MB | 0-0 | 21-66-41 | D05318P | 13 | DK | | D13910 | 10 | DK | | 150, 152-199 | | |
| 305B | 22 | PC | ME | 18-0 | 21-66-41 | D13914 | 8 | | | D13908 | A | | | 050-099 | | |
| 305B | 22 | PC | ME | 25-0 | 21-66-41 | D13914 | 8 | | | D13908 | A | | | 150, 152-199 | | |
| 305R | 22 | PC | ME | 0-0 | 21-66-41 | D13914 | 9 | | | D13908 | B | | | 050-099, 150, 152-199 | | |
| 305Y | 22 | PC | ME | 0-0 | 21-66-41 | D13914 | 10 | | | D13908 | C | | | 050-099, 150, 152-199 | | |
| W0772 | 286T0772 | | | L WHEEL WELL-L2-FLT CONT | | | | | | | | | | | | |
| 001 | 20 | UA | | 7-10 | 27-13-11 | D04402P | 1 | | | D02300 | 1 | | | ALL | | |
| 002 | 20 | UA | | 7-10 | 27-13-11 | D04402P | 2 | | | D02300 | 2 | | | ALL | | |
| 003 | 20 | UA | | 7-10 | 27-13-11 | D04402P | 3 | | | D02300 | 3 | | | ALL | | |
| 004 | 20 | UA | | 7-10 | 27-13-11 | D04402P | 4 | | | D02300 | 9 | | | ALL | | |
| 005 | 20 | UA | | 7-10 | 27-13-11 | D04402P | 5 | | | D02300 | 10 | | | ALL | | |
| W0774 | 286T0774 | | | R WHEEL WELL-R2-FLT CONT | | | | | | | | | | | | |
| 001 | 20 | UA | | 9-0 | 27-51-11 | D05418P | 1 | | | D02310 | 1 | | | ALL | | |
| 002 | 20 | UA | | 9-0 | 27-51-11 | D05418P | 2 | | | D02310 | 2 | | | ALL | | |
| 003 | 18 | UA | | 9-0 | 27-51-11 | D05418P | 3 | | | D02310 | 3 | | | ALL | | |
| 004 | 18 | UA | | 9-0 | 27-51-11 | D05418P | 4 | | | D02310 | 5 | | | ALL | | |
| 005 | 20 | UA | | 9-0 | 27-51-11 | D05418P | 5 | | | D02310 | 8 | | | ALL | | |
| W0775 | 286T0775 | | | HF R, TAIL DISC TO COUPLER | | | | | | | | | | | | |
| 001 | 20 | UA | | 33-11 | 23-11-21 | D04827J | 1 | | | D00087 | F | | | ALL | | |
| 002 | 20 | UA | | 33-11 | 23-11-21 | D04827J | 2 | | | D00087 | H | | | ALL | | |
| 003 | 20 | UA | | 33-11 | 23-11-21 | D04827J | 3 | | | D00087 | L | | | ALL | | |
| 004 | 20 | UA | | 33-11 | 23-11-21 | D04827J | 4 | | | D00087 | S | | | ALL | | |
| 005 | 20 | UA | | 33-11 | 23-11-21 | D04827J | 5 | | | D00087 | K | | | ALL | | |
| 006 | 20 | UA | | 33-11 | 23-11-21 | D04827J | 6 | | | D00087 | A | | | ALL | | |
| 009 | 18 | UA | | 1-6 | 23-11-21 | D00087 | D | DK | | GD00299 | A.. | N | | ALL | | |
| 010 | 20 | UA | | 1-4 | 23-11-11 | D00087 | X | | | SP00125 | | 1D | | ALL | | |
| 011 | 20 | UA | | 3-0 | 23-11-11 | D00087 | Y | | | SP00123 | | 9 | | ALL | | |
| 012 | 18 | UA | | 1-6 | 23-11-21 | D00087 | G | DK | | GD00583 | S.. | N | | ALL | | |
| W0776 | 286T0776 | | | R WHEEL WELL-R1-FLT CONT | | | | | | | | | | | | |
| 001 | 14 | UA | | 8-0 | 27-51-11 | D05420P | 1 | | | D02312 | 1 | | | ALL | | |
| 002 | 14 | UA | | 8-0 | 27-51-11 | D05420P | 2 | | | D02312 | 2 | | | ALL | | |
| 003 | 14 | UA | | 8-0 | 27-51-11 | D05420P | 3 | | | D02312 | 3 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0770

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0776 | 286T0776 | | | R WHEEL WELL-R1-FLT CONT (continued) | | | | | | | | | | | |
| 004 | 16 | | UA | 8-0 | 27-51-11 | D05420P | | 5 | | | D02312 | | 5 | | ALL |
| 005 | 18 | | UA | 8-0 | 27-51-11 | D05420P | | 6 | | | D02312 | | 6 | | ALL |
| 006 | 18 | | UA | 8-0 | 27-51-11 | D05420P | | 7 | | | D02312 | | 7 | | ALL |
| 007 | 16 | | UA | 8-0 | 27-51-11 | D05420P | | 8 | | | D02312 | | 8 | | ALL |
| W0777 | 286T0777 | | | HF L, TAIL DISC TO COUPLER | | | | | | | | | | | |
| 001 | 20 | | UA | 37-3 | 23-11-11 | D04825J | | 1 | | | D00085 | | F | | ALL |
| 002 | 20 | | UA | 37-3 | 23-11-11 | D04825J | | 2 | | | D00085 | | H | | ALL |
| 003 | 20 | | UA | 37-3 | 23-11-11 | D04825J | | 3 | | | D00085 | | L | | ALL |
| 004 | 20 | | UA | 37-3 | 23-11-11 | D04825J | | 4 | | | D00085 | | S | | ALL |
| 005 | 20 | | UA | 37-3 | 23-11-11 | D04825J | | 5 | | | D00085 | | K | | ALL |
| 006 | 20 | | UA | 37-3 | 23-11-11 | D04825J | | 6 | | | D00085 | | A | | ALL |
| 009 | 18 | | UA | 2-7 | 23-11-11 | D00085 | | D | DK | | GD00257 | | A.. | N | ALL |
| 010 | 20 | | UA | 2-7 | 23-11-11 | D00085 | | X | | | SP00123 | | | 9 | ALL |
| 011 | 20 | | UA | 2-7 | 23-11-11 | D00085 | | Y | | | SP00125 | | | 1D | ALL |
| 012 | 18 | | UA | 2-7 | 23-11-11 | D00085 | | G | DK | | GD00581 | | S.. | N | ALL |
| W0778 | 286T0778 | | | R WHEEL WELL-L2-FLT CONT | | | | | | | | | | | |
| 001 | 20 | | UA | 6-0 | 27-51-31 | D05414P | | 1 | | | D02304 | | 2 | | ALL |
| 002 | 20 | | UA | 6-0 | 27-51-31 | D05414P | | 2 | | | D02304 | | 4 | | ALL |
| 003 | 20 | | UA | 6-0 | 27-81-31 | D05414P | | 3 | | | D02304 | | 1 | | ALL |
| 004 | 20 | | UA | 6-0 | 27-81-31 | D05414P | | 4 | | | D02304 | | 3 | | ALL |
| 005 | 20 | | UA | 6-0 | 27-81-31 | D05414P | | 5 | | | D02304 | | 7 | | ALL |
| 006 | 20 | | UA | 7-0 | 27-51-51 | D05414P | | 6 | | | D02306 | | 3 | | 050-099 |
| 006 | 20 | | UA | 7-0 | 27-51-51 | D05414P | | 6 | | | D02306 | | 2 | | 150-199, 275-299 |
| 007 | 20 | | UA | 7-0 | 27-51-51 | D05414P | | 7 | | | D02306 | | 2 | | 050-099 |
| 007 | 20 | | UA | 7-0 | 27-51-51 | D05414P | | 7 | | | D02306 | | 3 | | 150-199, 275-299 |
| 008 | 20 | | UA | 7-0 | 27-51-51 | D05414P | | 8 | | | D02306 | | 1 | | ALL |
| 009 | 20 | | UA | 7-0 | 27-51-51 | D05414P | | 9 | | | D02306 | | 4 | | ALL |
| 011 | 20 | | UA | 3-0 | 27-81-31 | D05414P | | 13 | | | D72060 | | 3 | | 157, 167-199, 275-299 |
| 012 | 20 | | UA | 3-0 | 27-81-31 | D05414P | | 14 | | | D72060 | | 1 | | 157, 167-199, 275-299 |
| 013 | 20 | | UA | 3-0 | 27-81-31 | D05414P | | 12 | | | D72060 | | 2 | | 157, 167-199, 275-299 |
| W0779 | 286T0779 | | | WEATHER RADAR L | | | | | | | | | | | |
| 001 | 20 | | PA | 20-0 | 34-43-12 | D00391C | | 2 | | | SP00003 | | | 9 | ALL |
| 002 | 20 | | PA | 4-0 | 34-43-12 | D00391C | | 7 | | | GD00649 | | A.. | 2 | 050-099, 150-199 |
| 002 | 20 | | PA | 3-0 | 34-43-12 | D00391C | | 7 | | | GD00649 | | A.. | 2 | 275-299 |
| 003 | 20 | | PA | 4-0 | 34-43-12 | D00391C | | 11 | | | GD00649 | | D.. | 2 | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11
Section W0770
Page 4
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|-------|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0779 | 286T0779 | | | WEATHER RADAR L (continued) | | | | | | | | | | | | | |
| 003 | 20 | | PA | 3-0 | 34-43-12 | D00391C | | 11 | | | | | GD00649 | D.. | 2 | | 275-299 |
| 004 | 20 | | PA | 6-0 | 34-43-12 | D00391C | | 3 | | | | | D04917J | 24 | | | ALL |
| 005 | 20 | | PA | 6-0 | 34-43-12 | D00391C | | 8 | | | | | D04917J | 25 | | | ALL |
| 006 | 20 | | PA | 7-0 | 34-43-12 | GD00649 | | D.. | 2 | | | | D04917J | 22 | | | ALL |
| 007 | 22 | | PA | 6-0 | 34-43-12 | D00391B | | D11 | | | | | D04917J | 1 | | | ALL |
| 008 | 24 | | PK | 33-0 | 34-43-11 | D00391B | | G14 | | | | | D04889J | 1 | | | ALL |
| 009 | 24 | | PK | 24-0 | 34-43-12 | D00391B | | C06 | | | | | D00395 | K | | | ALL |
| 010 | 24 | | PK | 24-0 | 34-43-12 | D00391B | | D06 | | | | | D00395 | L | | | ALL |
| 011 | 24 | | PK | 24-0 | 34-43-12 | D00391B | | D07 | | | | | D00395 | M | | | ALL |
| 012 | 24 | | PK | 24-0 | 34-43-12 | D00391B | | B06 | | | | | D00395 | V | | | ALL |
| 013 | 24 | | PK | 24-0 | 34-43-12 | D00391B | | E06 | | | | | D00395 | U | | | ALL |
| 014 | 24 | | PK | 24-0 | 34-43-12 | D00391B | | E07 | | | | | D00395 | F- | | | ALL |
| 015 | 24 | | PK | 5-0 | 34-43-12 | D00391B | | D08 | | | | | D00483 | C | | | ALL |
| 016 | 24 | | PK | 21-0 | 34-43-12 | D00483 | | E | | | | | SP00001 | | 9 | | ALL |
| 017 | 24 | | PK | 14-0 | 34-43-12 | D00395 | | E | | | | | SP00001 | | 9 | | 050-099, 150-199 |
| 017 | 24 | | PK | 24-0 | 34-43-12 | D00395 | | E | | | | | SP00001 | | 9 | | 275-299 |
| 018 | 24 | | PK | 25-0 | 34-43-12 | D00395 | | D | | | | | D00483 | A | | | 050-099, 150-199 |
| 018 | 24 | | PK | 24-0 | 34-43-12 | D00395 | | D | | | | | D00483 | A | | | 275-299 |
| 019 | 20 | | PA | 6-0 | 34-43-12 | D00483 | | F | | | | | GD00649 | D.. | 2 | | 050-099, 150-199 |
| 019 | 20 | | PA | 5-0 | 34-43-12 | D00483 | | F | | | | | GD00649 | D.. | 2 | | 275-299 |
| 020 | 20 | | PA | 10-0 | 34-43-12 | D00395 | | A | | | | | GD02464 | D.. | 2 | | ALL |
| 021 | 20 | | PA | 2-11 | 33-13-18 | D00395 | | P | | | | | SP02280 | | 9 | | 050-099, 150-155, 162-165, 275-276 |
| 022 | 20 | | PA | 1-8 | 33-13-18 | D00395 | | E- | | | | | GD04452 | A.. | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 023 | 24 | | PK | 21-0 | 34-43-22 | D00483 | | D | | | | | SP00005 | | 9 | | ALL |
| 024 | 20 | | PA | 6-0 | 34-43-22 | D00483 | | B | | | | | GD00649 | D.. | 2 | | 050-099, 150-199 |
| 024 | 20 | | PA | 5-0 | 34-43-22 | D00483 | | B | | | | | GD00649 | D.. | 2 | | 275-299 |
| 025 | 20 | | PA | 15-0 | 34-43-12 | D00395 | | G | | | | | SP00341 | | 9 | | ALL |
| 026 | 20 | | UA | 1-6 | 34-43-12 | D00395 | | | | | | | GD04454 | S.. | 2 | | ALL |
| 201 | 20 | | UA | 1-6 | 34-43-12 | D00391B | | | | | | | GD00649 | S.. | 2 | | ALL |
| 201B | 22 | | PR IA | 6-0 | 34-43-12 | D00391B | | C14 | | | | | D04917J | 18 | | | ALL |
| 201R | 22 | | PR IA | 0-0 | 34-43-12 | D00391B | | C13 | | | | | D04917J | 17 | | | ALL |
| 201Z | | | IA | 0-0 | 34-43-12 | D00391B | | | | | | | D04917J | DED | | | ALL |
| 202B | 22 | | PR IB | 6-0 | 34-43-12 | D00391B | | E14 | | | | | D04917J | 20 | | | ALL |
| 202R | 22 | | PR IB | 0-0 | 34-43-12 | D00391B | | E13 | | | | | D04917J | 19 | | | ALL |
| 202Z | | | IB | 0-0 | 34-43-12 | D00391B | | | | | | | D04917J | DED | | | ALL |
| 203B | 22 | | PR IC | 6-0 | 34-43-12 | D00391B | | A14 | | | | | D04917J | 14 | | | ALL |
| 203R | 22 | | PR IC | 0-0 | 34-43-12 | D00391B | | A13 | | | | | D04917J | 13 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0770

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0779 | 286T0779 | | | WEATHER RADAR L (continued) | | | | | | | | | | | |
| 203Z | | | | IC | 0-0 | 34-43-12 | D00391B | | | FH | D04917J | DED | | | ALL |
| 204B | 22 | PR | | ID | 6-0 | 34-43-12 | D00391B | D15 | | | D04917J | 45 | | | ALL |
| 204R | 22 | PR | | ID | 0-0 | 34-43-12 | D00391B | E15 | | | D04917J | 44 | | | ALL |
| 204Z | | | | ID | 0-0 | 34-43-12 | D00391B | | | FH | D04917J | DED | | | ALL |
| 205 | 20 | UA | | | 1-6 | 34-43-12 | D00391B | | | FH | GD00649 | S.. | 2 | | ALL |
| 205B | 22 | PR | | IE | 6-0 | 34-43-12 | D00391B | B15 | | | D04917J | 16 | | | ALL |
| 205R | 22 | PR | | IE | 0-0 | 34-43-12 | D00391B | A15 | | | D04917J | 15 | | | ALL |
| 205Z | | | | IE | 0-0 | 34-43-12 | D00391B | | | FH | D04917J | DED | | | ALL |
| 206 | 20 | UA | | | 1-6 | 34-43-11 | D00391B | | | FN | GD00649 | S.. | 2 | | ALL |
| 206B | 24 | PW | | IF | 28-10 | 34-43-11 | D00391B | B04 | | | D04889J | 3 | | | 050-099, 150-199, 277-299 |
| 206B | 24 | PW | | IF | 27-10 | 34-43-11 | D00391B | B04 | | | D04889J | 3 | | | 275-276 |
| 206R | 24 | PW | | IF | 0-0 | 34-43-11 | D00391B | B03 | | | D04889J | 2 | | | ALL |
| 206Z | | | | | 0-0 | 34-43-11 | D00391B | | | FN | D04889J | 4 | | | ALL |
| 207W | 24 | 7K | | IG | 0-7 | 34-43-11 | D00391B | D02 | | | TB0201F | A002 | 2 | | ALL |
| 207WB | 24 | 7K | | IG | 0-0 | 34-43-11 | D00391B | D03 | | | TB0201F | C002 | 2 | | ALL |
| 207Z | | | | IG | 0-0 | 34-43-11 | D00391B | DED | | | GD00007 | S.. | 2 | | ALL |
| 208W | 24 | 7K | | IH | 33-0 | 34-43-11 | TB0201F | A002 | 2 | | D04889J | 5 | | | 050-099, 151 |
| 208W | 24 | 7K | | IH | 33-0 | 34-43-11 | TB0201F | A002 | 2 | | D04889J | 17 | | | 150, 152-199 |
| 208W | 24 | 7K | | IH | 33-0 | 34-43-11 | D04889J | 17 | | | TB0201F | A002 | 2 | | 275-299 |
| 208WB | 24 | 7K | | IH | 0-0 | 34-43-11 | TB0201F | C002 | 2 | | D04889J | 6 | | | 050-099, 151 |
| 208WB | 24 | 7K | | IH | 0-0 | 34-43-11 | TB0201F | C002 | 2 | | D04889J | 18 | | | 150, 152-199 |
| 208WB | 24 | 7K | | IH | 0-0 | 34-43-11 | D04889J | 18 | | | TB0201F | C002 | 2 | | 275-299 |
| 208Z | | | | IH | 0-0 | 34-43-11 | D04889J | 7 | | | GD00007 | S.. | 2 | | 050-099, 151 |
| 208Z | | | | IH | 0-0 | 34-43-11 | D04889J | 19 | | | GD00007 | S.. | 2 | | 150, 152-199, 275-299 |
| 209W | 24 | 7K | | II | 0-7 | 34-43-11 | D00391B | G02 | | | TB0201F | A003 | 2 | | ALL |
| 209WB | 24 | 7K | | II | 0-0 | 34-43-11 | D00391B | G03 | | | TB0201F | C003 | 2 | | ALL |
| 209Z | | | | II | 0-0 | 34-43-11 | D00391B | DED | | | GD00007 | S.. | 2 | | ALL |
| 210W | 24 | 7K | | IJ | 36-0 | 34-43-11 | TB0201F | A003 | 2 | | D04829J | 1 | | | 050-099, 150-199 |
| 210W | 24 | 7K | | IJ | 36-0 | 34-43-11 | D04829J | 1 | | | TB0201F | A003 | 2 | | 275-299 |
| 210WB | 24 | 7K | | IJ | 0-0 | 34-43-11 | TB0201F | C003 | 2 | | D04829J | 2 | | | 050-099, 150-199 |
| 210WB | 24 | 7K | | IJ | 0-0 | 34-43-11 | D04829J | 2 | | | TB0201F | C003 | 2 | | 275-299 |
| 210Z | | | | IJ | 0-0 | 34-43-11 | D04829J | 3 | | | GD00007 | S.. | 2 | | ALL |
| 211 | 20 | UA | | | 1-6 | 34-43-11 | D00391B | | | FL | GD00649 | S.. | 2 | | ALL |
| 211B | 24 | PW | | IK | 31-3 | 34-43-11 | D00391B | J04 | | | D04829J | 5 | | | ALL |
| 211R | 24 | PW | | IK | 0-0 | 34-43-11 | D00391B | J03 | | | D04829J | 4 | | | ALL |
| 211Z | | | | IK | 0-0 | 34-43-11 | D00391B | | | FL | D04829J | 6 | | | ALL |
| 212 | 20 | UA | | | 1-6 | 34-43-11 | D00391B | | | FP | GD00649 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0770

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0779 | 286T0779 | | | WEATHER RADAR L (continued) | | | | | | | | | | | |
| 212B | 24 | PW | IL | 28-10 | 34-43-11 | D00391B | J12 | | | | D04889J | 9 | | | 050-099, 150-199, 277-299 |
| 212B | 24 | PW | IL | 27-10 | 34-43-11 | D00391B | J12 | | | | D04889J | 9 | | | 275-276 |
| 212R | 24 | PW | IL | 0-0 | 34-43-11 | D00391B | J11 | | | | D04889J | 8 | | | ALL |
| 212Z | | | IL | 0-0 | 34-43-11 | D00391B | | | | FP | D04889J | 10 | | | ALL |
| 213 | 20 | UA | | 1-6 | 34-43-11 | D00391B | | | | FR | GD00649 | S.. | 2 | | ALL |
| 213B | 24 | PW | IM | 28-10 | 34-43-11 | D00391B | G13 | | | | D04889J | 12 | | | 050-099, 150-199, 277-299 |
| 213B | 24 | PW | IM | 27-10 | 34-43-11 | D00391B | G13 | | | | D04889J | 12 | | | 275-276 |
| 213R | 24 | PW | IM | 0-0 | 34-43-11 | D00391B | G12 | | | | D04889J | 11 | | | ALL |
| 213Z | | | IM | 0-0 | 34-43-11 | D00391B | | | | FR | D04889J | 13 | | | ALL |
| 214 | 20 | UA | | 1-6 | 34-43-12 | D00391B | | | | FJ | GD00649 | S.. | 2 | | ALL |
| 214B | 24 | PW | IN | 24-0 | 34-43-12 | D00391B | B08 | | | | D00395 | J- | | | ALL |
| 214R | 24 | PW | IN | 0-0 | 34-43-12 | D00391B | B07 | | | | D00395 | H- | | | ALL |
| 214Z | | | IN | 0-0 | 34-43-12 | D00391B | | | | FJ | D00395 | | | FI | ALL |
| 222 | 20 | UA | | 4-0 | 34-45-14 | GD00235 | S.. | 2 | | | STA0167 | REF | | IV | 050-099 |
| 222 | 20 | UA | | 1-0 | 34-45-14 | GD00235 | S.. | 2 | | | STA0167 | REF | | IV | 150-152, 275-276 |
| 222 | 20 | UA | | 3-0 | 34-45-14 | GD00235 | S.. | 2 | | | STA0167 | REF | | IV | 153-156, 162-166 |
| 222B | 24 | PW | IV | 30-0 | 34-45-14 | D04889J | 15 | | | | STA0167 | CAP | Y | | 050-099 |
| 222B | 24 | PW | IV | 28-0 | 34-45-14 | D04889J | 15 | | | | STA0167 | CAP | Y | | 150-154, 275-276 |
| 222B | 24 | PW | IV | 28-0 | SPARE | D04889J | 15 | | | | STA0167 | CAP | Y | | 155-156, 162-166 |
| 222R | 24 | PW | IV | 0-0 | 34-45-14 | D04889J | 14 | | | | STA0167 | CAP | Y | | 050-099, 150-156, 162-166, 275-276 |
| 222Z | | | IV | 0-0 | 34-45-14 | D04889J | 16 | | | | STA0167 | REF | | IV | 050-099, 150-154, 275-276 |
| 222Z | | | IV | 0-0 | SPARE | D04889J | 16 | | | | STA0167 | REF | | IV | 155-156, 162-166 |
| 225B | 20 | PB | IY | 0-0 | 33-13-18 | D00395 | E- | | | | SP05004 | | 9 | | 156-157, 166-199, 277-299 |
| 225R | 20 | PB | IY | 2-11 | 33-13-18 | D00395 | P | | | | SP02280 | | 9 | | 156-157, 166-199, 277-299 |
| 301B | 22 | PS | MA | 6-0 | 34-43-12 | D00391B | C11 | | | | D04917J | 53 | | | ALL |
| 301R | 22 | PS | MA | 0-0 | 34-43-12 | D00391B | C10 | | | | D04917J | 52 | | | ALL |
| 301Y | 22 | PS | MA | 0-0 | 34-43-12 | D00391B | C12 | | | | D04917J | 54 | | | ALL |
| 301Z | | | MA | 0-0 | 34-43-12 | D00391B | | | | FG | D04917J | DED | | | ALL |
| 302B | 22 | PS | MB | 6-0 | 34-43-12 | D00391B | E11 | | | | D04917J | 39 | | | ALL |
| 302R | 22 | PS | MB | 0-0 | 34-43-12 | D00391B | E10 | | | | D04917J | 40 | | | ALL |
| 302Y | 22 | PS | MB | 0-0 | 34-43-12 | D00391B | E12 | | | | D04917J | 38 | | | ALL |
| 302Z | | | MB | 0-0 | 34-43-12 | D00391B | | | | FG | D04917J | DED | | | ALL |
| 303B | 22 | PS | MC | 6-0 | 34-43-12 | D00391B | A11 | | | | D04917J | 42 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0770

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|------------------------------------|-------|----------|-------------|------|------|-----------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0779 | 286T0779 | | | WEATHER RADAR L (continued) | | | | | | | | | | | |
| 303R | 22 | PS | MC | | 0-0 | 34-43-12 | D00391B | A10 | | | D04917J | 41 | | | ALL |
| 303Y | 22 | PS | MC | | 0-0 | 34-43-12 | D00391B | A12 | | | D04917J | 43 | | | ALL |
| 303Z | | | MC | | 0-0 | 34-43-12 | D00391B | | | FH | D04917J | DED | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0770
Page 8 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0780 | 286T0780 | | | DOOR POSITION-ENTRY DOOR | | | | | | | | | | | | | |
| 201B | 24 | PL | A | 45-0 | 52-71-11 | D05102J | | 2 | | | | | SP00658 | | 9 | | 050-099 |
| 201B | 24 | PL | A | 47-0 | 52-71-11 | D05102J | | 2 | | | | | SP00658 | | 9 | | 150-199, 275-299 |
| 201R | 24 | PL | A | 0-0 | 52-71-11 | D05102J | | 1 | | | | | SP00656 | | 9 | | ALL |
| 202B | 24 | PL | B | 45-0 | 52-71-11 | D05102J | | 4 | | | | | SP00662 | | 9 | | 050-099 |
| 202B | 24 | PL | B | 47-0 | 52-71-11 | D05102J | | 4 | | | | | SP00662 | | 9 | | 150-199, 275-299 |
| 202R | 24 | PL | B | 0-0 | 52-71-11 | D05102J | | 3 | | | | | SP00660 | | 9 | | ALL |
| 203B | 24 | PL | C | 53-0 | 52-71-11 | D05102J | | 6 | | | | | SP00706 | | 9 | | ALL |
| 203R | 24 | PL | C | 0-0 | 52-71-11 | D05102J | | 5 | | | | | SP00704 | | 9 | | ALL |
| A-A | | | | 0-0 | 52-71-11 | SP00656 | | | | 9 | | | S00196 | RED | | | ALL |
| A-B | | | | 0-0 | 52-71-11 | SP00658 | | | | 9 | | | S00196 | BLU | | | ALL |
| B-A | | | | 0-0 | 52-71-11 | SP00660 | | | | 9 | | | S00197 | RED | | | ALL |
| B-B | | | | 0-0 | 52-71-11 | SP00662 | | | | 9 | | | S00197 | BLU | | | ALL |
| C-A | | | | 0-0 | 52-71-11 | SP00704 | | | | 9 | | | S00203 | RED | | | ALL |
| C-B | | | | 0-0 | 52-71-11 | SP00706 | | | | 9 | | | S00203 | BLU | | | ALL |
| W0781 | 286T0781 | | | WX RADAR,ANTENNA TO PRESS. SEAL | | | | | | | | | | | | | |
| 004 | 20 | PA | | 5-0 | 34-43-12 | D00491 | | | | I- | | | D04917P | | 24 | | ALL |
| 005 | 20 | PA | | 5-0 | 34-43-12 | D00491 | | | | Z- | | | D04917P | | 25 | | ALL |
| 006 | 20 | PA | | 5-0 | 34-43-12 | D00491 | | | | N- | | | D04917P | | 22 | | ALL |
| 007 | 20 | PA | | 5-0 | 34-43-12 | D00491 | | | | HH | | | D04917P | | 1 | | ALL |
| 201B | 20 | PR | IA | 5-0 | 34-43-12 | D00491 | | | | T- | | | D04917P | | 18 | | ALL |
| 201R | 20 | PR | IA | 0-0 | 34-43-12 | D00491 | | | | S- | | | D04917P | | 17 | | ALL |
| 201Z | | | IA | 0-0 | 34-43-12 | D00491 | | | | DD | | | D04917P | DED | | | ALL |
| 202B | 20 | PR | IB | 5-0 | 34-43-12 | D00491 | | | | Q- | | | D04917P | | 20 | | ALL |
| 202R | 20 | PR | IB | 0-0 | 34-43-12 | D00491 | | | | P- | | | D04917P | | 19 | | ALL |
| 202Z | | | IB | 0-0 | 34-43-12 | D00491 | | | | BB | | | D04917P | DED | | | ALL |
| 203B | 20 | PR | IC | 5-0 | 34-43-12 | D00491 | | | | V- | | | D04917P | | 14 | | ALL |
| 203R | 20 | PR | IC | 0-0 | 34-43-12 | D00491 | | | | U- | | | D04917P | | 13 | | ALL |
| 203Z | | | IC | 0-0 | 34-43-12 | D00491 | | | | EE | | | D04917P | DED | | | ALL |
| 204B | 20 | PR | ID | 5-0 | 34-43-12 | D00491 | | | | Y | | | D04917P | | 45 | | ALL |
| 204R | 20 | PR | ID | 0-0 | 34-43-12 | D00491 | | | | X | | | D04917P | | 44 | | ALL |
| 204Z | | | ID | 0-0 | 34-43-12 | D00491 | | | | R- | | | D04917P | DED | | | ALL |
| 205B | 20 | PR | IE | 5-0 | 34-43-12 | D00491 | | | | F- | | | D04917P | | 16 | | ALL |
| 205R | 20 | PR | IE | 0-0 | 34-43-12 | D00491 | | | | E- | | | D04917P | | 15 | | ALL |
| 205Z | | | IE | 0-0 | 34-43-12 | D00491 | | | | W- | | | D04917P | DED | | | ALL |
| 301B | 20 | PS | MA | 5-0 | 34-43-12 | D00491 | | | | E | | | D04917P | | 53 | | ALL |
| 301R | 20 | PS | MA | 0-0 | 34-43-12 | D00491 | | | | D | | | D04917P | | 52 | | ALL |
| 301Y | 20 | PS | MA | 0-0 | 34-43-12 | D00491 | | | | F | | | D04917P | | 54 | | ALL |
| 301Z | | | MA | 0-0 | 34-43-12 | D00491 | | | | A- | | | D04917P | DED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0781 | 286T0781 | | | WX RADAR,ANTENNA TO PRESS. SEAL (continued) | | | | | | | | | | | |
| 302B | 20 | PS | MB | 5-0 | 34-43-12 | D00491 | | B | | D04917P | 39 | | | ALL | |
| 302R | 20 | PS | MB | 0-0 | 34-43-12 | D00491 | | A | | D04917P | 40 | | | ALL | |
| 302Y | 20 | PS | MB | 0-0 | 34-43-12 | D00491 | | C | | D04917P | 38 | | | ALL | |
| 302Z | | | MB | 0-0 | 34-43-12 | D00491 | | W | | D04917P | DED | | | ALL | |
| 303B | 20 | PS | MC | 5-0 | 34-43-12 | D00491 | | H | | D04917P | 42 | | | ALL | |
| 303R | 20 | PS | MC | 0-0 | 34-43-12 | D00491 | | G | | D04917P | 41 | | | ALL | |
| 303Y | 20 | PS | MC | 0-0 | 34-43-12 | D00491 | | J | | D04917P | 43 | | | ALL | |
| 303Z | | | MC | 0-0 | 34-43-12 | D00491 | | D- | | D04917P | DED | | | ALL | |
| YAA | | | | 5-0 | 34-43-12 | D00491 | | REF | | D04917P | REF | | | ALL | |
| W0782 | 286T0782 | | | R WING RS - R2B - EEC CH. B | | | | | | | | | | | |
| 001 | 20 | PA | | 49-0 | 30-34-21 | D06584P | | 8 | | D06580J | 14 | | | 050-099 | |
| 001 | 20 | PA | | 59-0 | 30-34-21 | D06584P | | 8 | | D06580J | 14 | | | 150-199, 275-299 | |
| 009 | 24 | PV | AI | 49-0 | 73-21-14 | D06580J | | 2 | | D06584P | 2 | | | 050-099 | |
| 009 | 24 | PV | AI | 59-0 | 73-21-14 | D06580J | | 2 | | D06584P | 2 | | | 150-199, 275-299 | |
| 009Z | | | AI | 0-0 | 73-21-14 | D06580J | | =CC | M | D06584P | | | FE | 050-099, 150-199, 280-299 | |
| 009Z | | | AI | 0-0 | 73-21-14 | D06580J | | =CC | D | D06584P | | | FE | 275-278 | |
| 013 | 16 | PQ | AL | 49-0 | 73-21-20 | D06580J | | 13 | FM | D06584P | 7 | FL | | 050-099 | |
| 013 | 16 | PQ | AL | 59-0 | 73-21-20 | D06580J | | 13 | FM | D06584P | 7 | FL | | 150-199, 280-299 | |
| 013 | 16 | PQ | AM | 59-0 | 73-21-20 | D06580J | | 13 | FM | D06584P | 7 | FL | | 275-278 | |
| 013Z | | | AL | 0-0 | 73-21-20 | D06580J | | =CC | M | D06584P | | | FE | 050-099, 150-199, 280-299 | |
| 013Z | | | AM | 0-0 | 73-21-20 | D06580J | | =CC | D | D06584P | | | FE | 275-278 | |
| 014 | 24 | PV | AF | 49-0 | 73-21-11 | D06584P | | 9 | | D06580J | 8 | | | 050-099 | |
| 014 | 24 | PV | AF | 59-0 | 73-21-11 | D06584P | | 9 | | D06580J | 8 | | | 150-199, 280-299 | |
| 014 | 24 | PV | AN | 59-0 | 73-21-11 | D06580J | | 8 | | D06584P | 9 | | | 275-278 | |
| 014Z | | | AF | 0-0 | 73-21-11 | D06584P | | | | D06580J | =CC | M | | 050-099, 150-199, 280-299 | |
| 014Z | | | AN | 0-0 | 73-21-11 | D06580J | | =CC | D | D06584P | | | FE | 275-278 | |
| 018 | 24 | PV | AG | 49-0 | 73-21-11 | D06584P | | 10 | | D06580J | 9 | | | 050-099 | |
| 018 | 24 | PV | AG | 59-0 | 73-21-11 | D06584P | | 10 | | D06580J | 9 | | | 150-199, 280-299 | |
| 018 | 24 | PV | AR | 59-0 | 73-21-11 | D06580J | | 9 | | D06584P | 10 | | | 275-278 | |
| 018Z | | | AG | 0-0 | 73-21-11 | D06584P | | | | D06580J | =CC | M | | 050-099, 150-199, 280-299 | |
| 018Z | | | AR | 0-0 | 73-21-11 | D06580J | | =CC | D | D06584P | | | FE | 275-278 | |
| 027 | 22 | PA | | 28-0 | 78-36-21 | D11832 | | 8 | | D06584P | 6 | | | ALL | |
| 030 | 20 | UA | | 4-0 | 78-36-21 | D11832 | | 10 | | GD00561 | D.. | 2 | | 050-099 | |
| 030 | 20 | UA | | 4-0 | 78-36-21 | D11832 | | 10 | | GD03816 | D.. | E | * | 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|-----------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0782 | 286T0782 | | | R WING RS - R2B - EEC CH. B (continued) | | | | | | | | | | | | | |
| 030 | 20 | | UA | 5-0 | 78-36-21 | D11832 | | 10 | | | | | GD00561 | D.. | 2 | | 275-299 |
| 032 | 22 | | PA | 28-0 | 78-36-21 | D11832 | | 6 | | | | | D06584P | | 5 | | ALL |
| 043 | 20 | | UA | 4-0 | 78-36-21 | D11832 | | 3 | | | | | GD00561 | D.. | 2 | | 050-099 |
| 043 | 20 | | UA | 4-0 | 78-36-21 | D11832 | | 3 | | | | | GD03816 | D.. | E | * | 150-199 |
| 043 | 20 | | UA | 5-0 | 78-36-21 | D11832 | | 3 | | | | | GD00561 | D.. | 2 | | 275-299 |
| 052 | 22 | | PA | 28-0 | 78-36-21 | D11832 | | 4 | | | | | D06584P | | 1 | | ALL |
| 200B | 24 | | PW HY | 49-0 | 31-35-15 | D06580J | | 6 | | | | | D06584P | | 17 | | 050-099 |
| 200B | 24 | | PW HY | 59-0 | 31-35-15 | D06584P | | 17 | | | | | D06580J | | 6 | | 150-154 |
| 200B | 24 | | PW HY | 59-0 | 31-35-15 | D06580J | | 6 | | | | | D06584P | | 17 | | 155-199, 275-276, 278 |
| 200B | 24 | | PW HY | 59-0 | 31-31-27 | D06584P | | 17 | | | | | D06580J | | 6 | | 280-299 |
| 200R | 24 | | PW HY | 0-0 | 31-35-15 | D06580J | | 5 | | | | | D06584P | | 16 | | 050-099, 155-199, 275-276, 278 |
| 200R | 24 | | PW HY | 0-0 | 31-35-15 | D06584P | | 16 | | | | | D06580J | | 5 | | 150-154 |
| 200R | 24 | | PW HY | 0-0 | 31-31-27 | D06584P | | 16 | | | | | D06580J | | 5 | | 280-299 |
| 200Z | | | HY | 0-0 | 31-35-15 | D06580J | =CC | M | | | | | D06584P | | 18 | | 050-099, 155-199 |
| 200Z | | | HY | 0-0 | 31-35-15 | D06584P | | 18 | | | | | D06580J | =CC | D | | 150-154 |
| 200Z | | | HY | 0-0 | 31-35-15 | D06580J | =CC | D | | | | | D06584P | | 18 | | 275-276, 278 |
| 200Z | | | HY | 0-0 | 31-31-27 | D06584P | | 18 | | | | | D06580J | =CC | M | | 280-299 |
| 201B | 22 | | PR S | 49-0 | 73-21-14 | D06584P | | 25 | | | | | D06580J | | 21 | | 050-099 |
| 201B | 22 | | PR S | 59-0 | 73-21-14 | D06584P | | 25 | | | | | D06580J | | 21 | | 150-199, 280-299 |
| 201B | 22 | | PR IA | 59-0 | 73-21-14 | D06580J | | 21 | | | | | D06584P | | 25 | | 275-278 |
| 201R | 22 | | PR S | 0-0 | 73-21-14 | D06584P | | 26 | | | | | D06580J | | 22 | | 050-099, 150-199, 280-299 |
| 201R | 22 | | PR IA | 0-0 | 73-21-14 | D06580J | | 22 | | | | | D06584P | | 26 | | 275-278 |
| 201Z | | | S | 0-0 | 73-21-14 | D06584P | | | | | FC | | D06580J | =CC | M | | 050-099, 150-199, 280-299 |
| 201Z | | | IA | 0-0 | 73-21-14 | D06580J | =CC | D | | | | | D06584P | | | FC | 275-278 |
| 202B | 24 | | PW T | 49-0 | 73-21-14 | D06580J | | 17 | | | | | D06584P | | 27 | | 050-099 |
| 202B | 24 | | PW T | 59-0 | 73-21-14 | D06580J | | 17 | | | | | D06584P | | 27 | | 150-199, 280-299 |
| 202B | 24 | | PW IB | 59-0 | 73-21-14 | D06580J | | 17 | | | | | D06584P | | 27 | | 275-278 |
| 202R | 24 | | PW T | 0-0 | 73-21-14 | D06580J | | 18 | | | | | D06584P | | 28 | | 050-099, 150-199, 280-299 |
| 202R | 24 | | PW IB | 0-0 | 73-21-14 | D06580J | | 18 | | | | | D06584P | | 28 | | 275-278 |
| 202Z | | | T | 0-0 | 73-21-14 | D06580J | =CC | M | | | | | D06584P | | | FC | 050-099, 150-199, 280-299 |
| 202Z | | | IB | 0-0 | 73-21-14 | D06580J | =CC | D | | | | | D06584P | | | FC | 275-278 |
| 203B | 24 | | PW IC | 77-0 | 73-21-13 | D04736J | | 11 | | | | | D06580J | | 15 | | 050-099, 150-199, 280-299 |
| 203B | 24 | | PW IC | 77-0 | 73-21-13 | D06580J | | 15 | | | | | D04736J | | 11 | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------|--|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0782 | 286T0782 | | | | R WING RS - R2B - EEC CH. B (continued) | | | | | | | | | | |
| 203R | 24 | PW | IC | 0-0 | 73-21-13 | D04736J | | 12 | | | D06580J | | 16 | | 050-099, 150-199, 280-299 |
| 203R | 24 | PW | IC | 0-0 | 73-21-13 | D06580J | | 16 | | | D04736J | | 12 | | 275-278 |
| 203Z | | | IC | 0-0 | 73-21-13 | D04736J | | | | FX | D06580J | | = CC | M | 050-099, 150-199, 280-299 |
| 203Z | | | IC | 0-0 | 73-21-13 | D06580J | | = CC | D | | D04736J | | | | 275-278 |
| 210B | 24 | PW | IJ | 49-0 | 73-21-14 | D06580J | | 12 | | | D06584P | | 4 | | 050-099 |
| 210B | 24 | PW | IJ | 59-0 | 73-21-14 | D06580J | | 12 | | | D06584P | | 4 | | 150-199, 275-299 |
| 210R | 24 | PW | IJ | 0-0 | 73-21-14 | D06580J | | 11 | | | D06584P | | 3 | | ALL |
| 210Z | | | IJ | 0-0 | 73-21-14 | D06580J | | = CC | M | | D06584P | | | | 050-099, 150-199, 280-299 |
| 210Z | | | IJ | 0-0 | 73-21-14 | D06580J | | = CC | D | | D06584P | | | | 275-278 |
| 211B | 24 | PW | AJ | 49-0 | 73-21-17 | D06580J | | 10 | | | D06584P | | 13 | | 050-099 |
| 211B | 24 | PW | AJ | 59-0 | 73-21-17 | D06580J | | 10 | | | D06584P | | 13 | | 150-199, 280-299 |
| 211B | 24 | PW | IK | 59-0 | 73-21-17 | D06580J | | 10 | | | D06584P | | 13 | | 275-278 |
| 211R | 24 | PW | AJ | 0-0 | 73-21-12 | D06580J | | 1 | | | D06584P | | 14 | | 050-099, 150-199, 280-299 |
| 211R | 24 | PW | IK | 0-0 | 73-21-12 | D06580J | | 1 | | | D06584P | | 14 | | 275-278 |
| 211Z | | | AJ | 0-0 | 73-21-12 | D06580J | | = CC | M | | D06584P | | 15 | | 050-099, 150-199, 280-299 |
| 211Z | | | IK | 0-0 | 73-21-12 | D06580J | | = CC | D | | D06584P | | 15 | | 275-278 |
| 213B | 24 | PW | IM | 49-0 | 77-12-11 | D06584P | | 23 | | | D06580J | | 3 | | 050-099 |
| 213B | 24 | PW | IM | 59-0 | 77-12-11 | D06584P | | 23 | | | D06580J | | 3 | | 150-199, 280-299 |
| 213B | 24 | PW | IM | 59-0 | 77-12-11 | D06580J | | 3 | | | D06584P | | 23 | | 275-278 |
| 213R | 24 | PW | IM | 0-0 | 77-12-11 | D06584P | | 22 | | | D06580J | | 4 | | 050-099, 150-199, 280-299 |
| 213R | 24 | PW | IM | 0-0 | 77-12-11 | D06580J | | 4 | | | D06584P | | 22 | | 275-278 |
| 213Z | | | IM | 0-0 | 77-12-11 | D06584P | | 24 | | | D06580J | | = CC | M | 050-099, 150-199, 280-299 |
| 213Z | | | IM | 0-0 | 77-12-11 | D06580J | | = CC | D | | D06584P | | 24 | | 275-278 |
| 302B | 24 | PX | MB | 77-0 | 73-21-13 | D04736J | | 7 | | | D06580J | | 27 | | 050-099, 150-199, 280-299 |
| 302B | 24 | PX | MB | 77-0 | 73-21-13 | D06580J | | 27 | | | D04736J | | 7 | | 275-278 |
| 302R | 24 | PX | MB | 0-0 | 73-21-13 | D04736J | | 6 | | | D06580J | | 26 | | 050-099, 150-199, 280-299 |
| 302R | 24 | PX | MB | 0-0 | 73-21-13 | D06580J | | 26 | | | D04736J | | 6 | | 275-278 |
| 302Y | 24 | PX | MB | 0-0 | 73-21-13 | D04736J | | 8 | | | D06580J | | 25 | | 050-099, 150-199, 280-299 |
| 302Y | 24 | PX | MB | 0-0 | 73-21-13 | D06580J | | 25 | | | D04736J | | 8 | | 275-278 |

WIRE LIST

D280T132

91-21-11
Section W0780
Page 4
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|---------|------|--------|------------------------------------|---------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0782 | 286T0782 | | | R WING RS - R2B - EEC CH. B (continued) | | | | | | | | | | | | |
| 302Z | | | | MB | 0-0 | 73-21-13 | D04736J | | | | FY | D06580J | =CC | M | 050-099, 150-199, 280-299 | |
| 302Z | | | | MB | 0-0 | 73-21-13 | D06580J | =CC | D | | | D04736J | | | FY | 275-278 |
| 541 | 20 | UA | | | 2-0 | 73-21-13 | D04736J | | | | FY | GD00561 | S.. | 2 | 050-099, 150-156, 162-166, 275-276 | |
| 542 | 20 | UA | | | 2-0 | 73-21-13 | D04736J | | | | FX | GD00561 | S.. | 2 | 050-099, 150-156, 162-166, 275-276 | |
| FR2 | | | | | 0-0 | 73-21-13 | D04736J | | | | FX | GD00561 | S.. | 2 | 157, 167-199, 277-299 | |
| FR3 | | | | | 0-0 | 73-21-13 | D04736J | | | | FY | GD00561 | S.. | 2 | 157, 167-199, 277-299 | |
| FRC | | | | | 0-0 | 73-21-14 | D06584P | | | | FC | D06584P | | 29 | ALL | |
| FRE | | | | | 0-0 | 73-21-14 | D06584P | | | | FE | D06584P | | 12 | ALL | |
| FRX | | | | | 0-0 | 73-21-13 | D04736J | | | | FX | D04736J | | 10 | ALL | |
| FRY | | | | | 0-0 | 73-21-13 | D04736J | | | | FY | D04736J | | 1 | ALL | |
| W0783 | 286T0783 | | | CROSSAISLE LIGHTS JUMPER BUNDLE | | | | | | | | | | | | |
| 001 | 20 | PA | | | 2-0 | 33-51-16 | D02589 | | C | | | D02589 | | D | 050-099, 150-199 | |
| W0784 | 286T0784 | | | WING ILLUMINATION LIGHTS, EMERGENCY LIGHTS | | | | | | | | | | | | |
| 001 | 20 | PA | | | 32-11 | 33-41-11 | D05076P | | | 1 | | L00061 | 115V | E | 050-099 | |
| 001 | 18 | PA | | | 36-0 | 33-41-11 | D05076P | | | 1 | DL | L00061 | 115V | E | 150-199, 275-299 | |
| 002 | 14 | PA | | | 2-6 | 33-41-11 | L00061 | | | | RTN | GD01442 | A.. | E | 050-099 | |
| 002 | 14 | PA | | | 3-1 | 33-41-11 | L00061 | | | | RTN | GD05082 | A.. | E | 150-199, 275-299 | |
| 003 | 20 | PA | | | 57-9 | 33-51-11 | D05076P | | | 3 | | D05078P | | 2 | 050-099 | |
| 003 | 20 | PA | | | 68-0 | 33-51-11 | D05076P | | | 3 | | D05078P | | 2 | 150-199, 275-299 | |
| 004 | 20 | PA | | | 1-6 | 33-51-11 | SM00024 | | | | S | D01084 | | 2 | 050-099, 150-199 | |
| 004 | 20 | PA | | | 17-0 | 33-51-11 | D05076P | | | 4 | | D01084 | | 2 | 275-299 | |
| 005 | 22 | PA | | | 1-6 | 33-51-11 | SM00028 | | | | S | D01084 | | 4 | 050-099, 150-199 | |
| 005 | 22 | PA | | | 17-0 | 33-51-11 | D05076P | | | 5 | | D01084 | | 4 | 275-299 | |
| 006 | 22 | PA | | | 57-9 | 33-51-11 | D05076P | | | 6 | | D05078P | | 3 | 050-099 | |
| 006 | 22 | PA | | | 68-0 | 33-51-11 | D05076P | | | 6 | | D05078P | | 3 | 150-199, 275-299 | |
| 007 | 22 | PA | | | 1-6 | 33-51-11 | SM00011 | | | | S | D01084 | | 3 | 050-099, 275-299 | |
| 007 | 22 | PA | | | 0-6 | 33-51-11 | SM00011 | | | | S | D01084 | | 3 | 150-199 | |
| 011 | 22 | PA | | | 15-6 | 33-51-11 | SM00005 | | | | S | D01084 | | 8 | 050-099 | |
| 011 | 22 | PA | | | 0-6 | 33-51-11 | SM00005 | | | | S | D01084 | | 8 | 150-199 | |
| 011 | 22 | PA | | | 1-6 | 33-51-11 | SM00005 | | | | S | D01084 | | 8 | 275-299 | |
| 012 | 22 | PA | | | 7-5 | 33-51-11 | D05076P | | | 12 | | SM00005 | | | S | 050-099 |
| 012 | 22 | PA | | | 23-7 | 33-51-11 | D05076P | | | 12 | | SM00005 | | | S | 150-199 |
| 012 | 22 | PA | | | 17-0 | 33-51-11 | D05076P | | | 12 | | SM00005 | | | S | 275-299 |
| 013 | 22 | PA | | | 50-10 | 33-51-11 | SM00005 | | | | S | D05078P | | 7 | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0784 | 286T0784 | | | WING ILLUMINATION LIGHTS, EMERGENCY LIGHTS (continued) | | | | | | | | | | | |
| 013 | 22 | | PA | | 73-7 | 33-51-11 | SM00005 | | | | S | | | | 150-199 |
| 013 | 22 | | PA | | 72-1 | 33-51-11 | SM00005 | | | | S | | | | 275-299 |
| 014 | 20 | | PA | | 2-3 | 33-51-11 | D01084 | | 7 | | | | S.. | E | 050-099 |
| 014 | 20 | | PA | | 2-3 | 33-51-11 | D01084 | | 7 | | | | S.. | E | 150-199 |
| 014 | 20 | | PA | | 2-3 | 33-51-11 | D01084 | | 7 | | | | S.. | E | 275-299 |
| 015 | 22 | | PA | | 0-7 | 33-51-11 | D01084 | | 5 | | | | | | ALL |
| 016 | 20 | | PA | | 1-8 | 33-51-11 | D01084 | | 1 | | | | D.. | E | 050-099 |
| 016 | 20 | | PA | | 2-0 | 33-51-11 | D01084 | | 1 | | | | D.. | E | 150-199 |
| 016 | 20 | | PA | | 1-8 | 33-51-11 | D01084 | | 1 | | | | D.. | E | 275-299 |
| 017 | 20 | | PA | | 57-9 | 33-51-11 | D05076P | | 2 | | | | | | 050-099 |
| 017 | 20 | | PA | | 68-0 | 33-51-11 | D05076P | | 2 | | | | | | 150-199, 275-299 |
| 025 | 20 | | PA | | 39-3 | 33-51-13 | D01084 | | 16 | | | | | 1 | C |
| 025 | 20 | | PA | | 37-9 | 33-51-13 | D01084 | | 16 | | | | | 1 | C |
| 025 | 20 | | PA | | 38-6 | 33-51-13 | D01084 | | 16 | | | | REF | * | 280-299 |
| 026 | 20 | | PA | | 27-9 | 33-51-13 | D01084 | | 15 | | | | | 1 | C |
| 026 | 20 | | PA | | 32-9 | 33-51-13 | D01084 | | 15 | | | | | 1 | C |
| 026 | 20 | | PA | | 31-3 | 33-51-13 | D01084 | | 15 | | | | | 1 | C |
| 026 | 20 | | PA | | 31-3 | 33-51-13 | D01084 | | 15 | | | | REF | * | 280-299 |
| 027 | 22 | | PA | | 20-8 | 33-51-13 | D01084 | | 14 | | | | | 1 | C |
| 027 | 22 | | PA | | 25-7 | 33-51-13 | D01084 | | 14 | | | | | 1 | C |
| 027 | 22 | | PA | | 24-2 | 33-51-13 | D01084 | | 14 | | | | | 1 | C |
| 028 | 18 | | PA | | 33-1 | 33-51-13 | D01084 | | 13 | | DK | | | 1 | C |
| 028 | 18 | | PA | | 35-5 | 33-51-13 | D01084 | | 13 | | DK | | | 1 | C |
| 028 | 20 | | PA | | 23-7 | 33-51-13 | D01084 | | 13 | | DK | | | 10 | |
| 028 | 22 | | PA | | 16-5 | 33-51-13 | D01084 | | 13 | | | | | 1 | C |
| 029 | 18 | | PA | | 22-3 | 33-51-13 | L00315 | | 1 | | C | | | 12 | DK |
| 029 | 18 | | PA | | 40-6 | 33-51-13 | L00315 | | 1 | | C | | | 12 | DK |
| 029 | 18 | | PA | | 40-6 | 33-51-13 | L00315 | | 1 | | C | * | | 12 | DK |
| 029 | 18 | | PA | | 28-3 | 33-51-13 | L00315 | | 1 | | C | | | 12 | DK |
| 029 | 18 | | PA | | 28-5 | 33-51-13 | L00315 | | 1 | | C | | | 12 | DK |
| 030 | 20 | | PA | | 21-10 | 33-51-13 | D01084 | | 11 | | | | | 10 | |
| 030 | 22 | | PA | | 33-4 | 33-51-13 | D01084 | | 11 | | | | | 1 | C |
| 030 | 20 | | PA | | 33-4 | 33-51-13 | D01084 | | 11 | | | | | 1 | C |
| 030 | 22 | | PA | | 26-4 | 33-51-13 | D01084 | | 11 | | | | | 1 | C |
| 031 | 22 | | PA | | 34-8 | 33-51-13 | D01084 | | 10 | | | | | 1 | C |
| 031 | 22 | | PA | | 1-6 | 33-51-13 | D01084 | | 10 | | | | | | S |
| 031 | 20 | | PA | | 1-6 | 33-51-13 | D01084 | | 10 | | | | | | S |
| 035 | 20 | | PA | | 6-1 | 33-51-13 | L00313 | | 2 | | C | | | D.. | 2 |
| 036 | 20 | | PA | | 7-3 | 33-51-13 | L00314 | | 2 | | C | | | D.. | 2 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0784 | 286T0784 | | | WING ILLUMINATION LIGHTS, EMERGENCY LIGHTS (continued) | | | | | | | | | | | | | |
| 036 | 20 | PA | | 6-11 | 33-51-13 | L00314 | | 2 | C | | | | GD03932 | D.. | 2 | | 275-299 |
| 037 | 18 | PA | | 11-4 | 33-51-13 | L00315 | | 2 | C | | | | GD02534 | D.. | E | | 050-099 |
| 037 | 18 | PA | | 25-8 | 33-51-13 | L00315 | | 2 | C | | | | GD02534 | D.. | E | | 150-199 |
| 037 | 18 | PA | | 8-10 | 33-51-13 | L00315 | | 2 | C | | | | GD03932 | D.. | 2 | | 275-278 |
| 037 | 18 | PA | | 9-0 | 33-51-13 | L00315 | | 2 | C | | | | GD03932 | D.. | 2 | | 280-299 |
| 038 | 20 | PA | | 14-11 | 33-51-13 | L00316 | | 2 | C | | | | GD03932 | D.. | 2 | | 050-099 |
| 038 | 20 | PA | | 26-2 | 33-51-13 | L00316 | | 2 | C | | | | GD02534 | D.. | E | | 150-199 |
| 038 | 20 | PA | | 6-1 | 33-51-13 | L00316 | | 2 | C | | | | GD02534 | D.. | E | | 275-299 |
| 039 | 20 | PA | | 5-4 | 33-51-13 | L00317 | | 2 | C | | | | GD02536 | D.. | E | | 050-099 |
| 039 | 20 | PA | | 4-10 | 33-51-13 | L00317 | | 2 | C | | | | GD02536 | D.. | E | | 150-199, 275-299 |
| 040 | 20 | PA | | 5-0 | 33-51-13 | L00318 | | 2 | C | | | | GD02538 | D.. | E | | 050-099 |
| 040 | 20 | PA | | 6-2 | 33-51-13 | L00318 | | 2 | C | | | | GD02538 | D.. | E | | 150-199, 275-278 |
| 040 | 20 | PA | | 6-2 | 33-51-13 | ST0631L | | REF | * | | | | GD02538 | D.. | E | | 280-299 |
| 041 | 20 | PA | | 5-0 | 33-51-13 | L00319 | | 2 | C | | | | GD02540 | D.. | E | | 050-099 |
| 041 | 20 | PA | | 11-1 | 33-51-13 | L00780 | | 2 | C | | | | GD05076 | D.. | E | | 150-199, 275-278 |
| 041 | 20 | PA | | 6-2 | 33-51-13 | ST0654L | | REF | * | | | | GD05076 | D.. | E | | 280-299 |
| 058 | 22 | PA | | 57-9 | 33-51-21 | D05076P | | 20 | | | | | D05078P | 14 | | | 050-099 |
| 058 | 22 | PA | | 68-0 | 33-51-21 | D05076P | | 20 | | | | | D05078P | 14 | | | 150-199, 275-299 |
| 059 | 22 | PA | | 57-9 | 33-51-21 | D05076P | | 19 | | | | | D05078P | 15 | | | 050-099 |
| 059 | 22 | PA | | 68-0 | 33-51-21 | D05076P | | 19 | | | | | D05078P | 15 | | | 150-199, 275-299 |
| 061 | 22 | PA | | 57-9 | 33-51-21 | D05076P | | 21 | | | | | D05078P | 17 | | | 050-099 |
| 061 | 22 | PA | | 68-0 | 33-51-21 | D05076P | | 21 | | | | | D05078P | 17 | | | 150-199, 275-299 |
| 075 | 22 | PA | | 42-1 | 33-22-21 | D05076P | | 36 | | | | | D12086J | = 1 | | | 150-199 |
| 077 | 22 | PA | | 0-7 | 33-51-13 | D01084 | | 20 | | | | | D01084 | 24 | | | ALL |
| 078 | 20 | PA | | 7-1 | 33-22-21 | D08126P | | = 1 | | | | | GD04198 | A.. | 2 | | 050-099 |
| 079 | 22 | PA | | 47-1 | 33-22-21 | D05076P | | 36 | | | | | D08124J | = 1 | | | 050-099 |
| 081 | 22 | PA | | 32-3 | 33-51-13 | L00611 | | 1 | C | | | | SM00001 | | S | | 150-199 |
| 081 | 22 | PA | | 26-8 | 33-51-13 | L00611 | | 1 | C | | | | SM00001 | | S | | 275-299 |
| 082 | 20 | PA | | 10-10 | 33-51-13 | L00611 | | 2 | C | | | | GD00760 | D.. | 2 | | 150-199 |
| 082 | 20 | PA | | 10-6 | 33-51-13 | L00611 | | 2 | C | | | | GD00760 | D.. | 2 | | 275-299 |
| 084 | 22 | PA | | 42-3 | 33-51-13 | L00313 | | 1 | C | | | | SM00001 | | S | | 150-199 |
| 084 | 22 | PA | | 35-6 | 33-51-13 | L00313 | | 1 | C | | | | SM00001 | | S | | 275-299 |
| 085 | 14 | PA | | 2-6 | 33-41-11 | L00061 | | GND | E | | | | GD04178 | S.. | E | | 050-099 |
| 085 | 14 | PA | | 3-1 | 33-41-11 | L00061 | | GND | E | | | | GD05084 | S.. | E | | 150-199, 275-299 |
| 093 | 20 | PA | | 2-6 | 33-51-21 | D01648 | | 7 | | | | | GD02720 | S.. | E | | 050-099 |
| 093 | 20 | PA | | 1-10 | 33-51-21 | D01648 | | 7 | | | | | GD02720 | S.. | E | | 150-199, 275-299 |
| 094 | 20 | PA | | 2-0 | 33-51-21 | D01648 | | 1 | | | | | GD02718 | D.. | E | | 050-099 |
| 094 | 20 | PA | | 1-9 | 33-51-21 | D01648 | | 1 | | | | | GD02718 | D.. | E | | 150-199, 275-299 |
| 095 | 22 | PA | | 92-2 | 33-51-21 | D01648 | | 3 | | | | | SM00011 | | S | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0784 | 286T0784 | | | WING ILLUMINATION LIGHTS, EMERGENCY LIGHTS (continued) | | | | | | | | | | | | | | |
| 095 | 22 | | PA | 119-8 | 33-51-21 | D01648 | | 3 | | | | | | SM00011 | | S | | 150-199 |
| 095 | 22 | | PA | 118-3 | 33-51-21 | D01648 | | 3 | | | | | | SM00011 | | S | | 275-299 |
| 096 | 22 | | PA | 92-7 | 33-51-21 | D01648 | | 4 | | | | | | D05076P | 14 | | | 050-099 |
| 096 | 22 | | PA | 113-7 | 33-51-21 | D01648 | | 4 | | | | | | D05076P | 14 | | | 150-199 |
| 096 | 22 | | PA | 114-1 | 33-51-21 | D01648 | | 4 | | | | | | D05076P | 14 | | | 275-299 |
| 097 | 20 | | PA | 92-7 | 33-51-21 | D01648 | | 2 | | | | | | D05076P | 16 | | | 050-099 |
| 097 | 20 | | PA | 114-1 | 33-51-21 | D01648 | | 2 | | | | | | D05076P | 16 | | | 150-199, 275-278 |
| 097 | 20 | | PA | 114-4 | 33-51-21 | D01648 | | 2 | | | | | | D05076P | 16 | | | 280-299 |
| 098 | 22 | | PA | 92-7 | 33-51-21 | D01648 | | 8 | | | | | | D05076P | 17 | | | 050-099 |
| 098 | 22 | | PA | 114-1 | 33-51-21 | D01648 | | 8 | | | | | | D05076P | 17 | | | 150-199, 275-278 |
| 098 | 22 | | PA | 114-4 | 33-51-21 | D01648 | | 8 | | | | | | D05076P | 17 | | | 280-299 |
| 099 | 20 | | PA | 0-7 | 33-51-21 | D01648 | | 24 | | | | | | D01648 | 20 | | | ALL |
| 101 | 22 | | PA | 0-7 | 33-51-21 | D01648 | | 6 | | | | | | D01648 | 5 | | | ALL |
| 102 | 16 | | PA | 4-2 | 33-51-21 | D06322P | | = 1 | | | | | | GD02712 | D.. | E | | 050-099 |
| 102 | 16 | | PA | 4-3 | 33-51-21 | D06322P | | = 1 | | | | | | GD02712 | D.. | E | | 150-199, 275-299 |
| 103 | 12 | | PA | 36-10 | 33-51-21 | SM00020 | | | | S | | | | SM00002 | | S | | 050-099 |
| 103 | 12 | | PA | 39-5 | 33-51-21 | SM00020 | | | | S | | | | SM00002 | | S | | 150-199, 275-299 |
| 104 | 20 | | PA | 1-6 | 33-51-21 | D01648 | | 11 | | | | | | SM00002 | | S | | ALL |
| 105 | 20 | | PA | 1-6 | 33-51-21 | D01648 | | 10 | | | | | | SM00003 | | S | | ALL |
| 106 | 20 | | PA | 5-2 | 33-51-21 | D01648 | | 12 | | | | | | L00645 | 1 | D | | 050-099 |
| 106 | 20 | | PA | 33-8 | 33-51-21 | D01648 | | 12 | | | | | | L00645 | 1 | D | | 150-199, 275-299 |
| 107 | 20 | | PA | 3-8 | 33-51-21 | L00645 | | 2 | D | | | | | GD04212 | D.. | E | | 050-099 |
| 107 | 20 | | PA | 2-3 | 33-51-21 | L00645 | | 2 | D | | | | | GD02714 | D.. | E | | 150-199, 275-299 |
| 108 | 14 | | PA | 31-10 | 33-51-21 | L00396 | | 1 | D | | | | | SM00003 | | S | | 050-099 |
| 108 | 14 | | PA | 43-9 | 33-51-21 | L00396 | | 1 | D | | | | | SM00003 | | S | | 150-199, 275-299 |
| 109 | 14 | | PA | 2-3 | 33-51-21 | L00396 | | 2 | D | | | | | GD02714 | D.. | E | | 050-099 |
| 109 | 14 | | PA | 2-2 | 33-51-21 | L00396 | | 2 | D | | | | | GD04814 | D.. | E | | 150-199, 275-299 |
| 110 | 22 | | PA | 21-10 | 33-51-11 | D05076P | | 7 | | | | | | SM00011 | | S | | 050-099 |
| 110 | 22 | | PA | 23-7 | 33-51-11 | D05076P | | 7 | | | | | | SM00011 | | S | | 150-199 |
| 110 | 22 | | PA | 17-0 | 33-51-11 | D05076P | | 7 | | | | | | SM00011 | | S | | 275-299 |
| 115 | 16 | | PA | 0-5 | 33-51-21 | SM00020 | | | | S | | | | D06320J | = 1 | | | 050-099 |
| 115 | 16 | | PA | 0-6 | 33-51-21 | SM00020 | | | | S | | | | D06320J | = 1 | | | 150-199, 275-299 |
| 119 | 22 | | PA | 39-3 | 33-51-13 | D01084 | | 9 | | | | | | L00316 | 1 | C | | 050-099 |
| 119 | 22 | | PA | 41-0 | 33-51-13 | D01084 | | 9 | | | | | | L00316 | 1 | C | | 150-157 |
| 119 | 18 | | PA | 33-3 | 33-51-13 | D01084 | | 9 | DK | | | | | L00324 | 1 | C | | 162-199 |
| 119 | 20 | | PA | 1-8 | 33-51-17 | D01084 | | 9 | | | | | | D11706 | = 1 | | | 275-299 |
| 120 | 20 | | PA | 1-10 | 33-51-17 | D11708 | | = 1 | | | | | | GD04216 | D.. | E | | 275-299 |
| 142 | 20 | | PA | 8-10 | 33-51-13 | L00324 | | 2 | C | | | | | GD03932 | D.. | 2 | | 050-099 |
| 142 | 20 | | PA | 5-2 | 33-51-13 | L00324 | | 2 | C | | | | | GD03932 | D.. | 2 | | 162-199 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0784 | 286T0784 | | | WING ILLUMINATION LIGHTS, EMERGENCY LIGHTS (continued) | | | | | | | | | | | | | |
| 146 | 20 | | PA | 13-9 | 33-51-13 | L01132 | | 2 | C | | | | GD03932 | D.. | 2 | | 150-157 |
| 149 | 20 | | PA | 2-3 | 33-51-13 | L00315 | | 1 | C | * | | | L00316 | | 1 | C | 162-199 |
| 201B | 24 | | PL | A | 57-9 | 52-71-11 | D05076P | | 23 | | | | D05078P | | 23 | | 050-099 |
| 201B | 24 | | PL | A | 68-0 | 52-71-11 | D05076P | | 23 | | | | D05078P | | 23 | | 150-199, 275-299 |
| 201R | 24 | | PL | A | 0-0 | 52-71-11 | D05076P | | 22 | | | | D05078P | | 22 | | ALL |
| 202B | 24 | | PL | B | 57-9 | 52-71-11 | D05076P | | 25 | | | | D05078P | | 25 | | 050-099 |
| 202B | 24 | | PL | B | 68-0 | 52-71-11 | D05076P | | 25 | | | | D05078P | | 25 | | 150-199, 275-299 |
| 202R | 24 | | PL | B | 0-0 | 52-71-11 | D05076P | | 24 | | | | D05078P | | 24 | | ALL |
| 203B | 24 | | PL | C | 57-9 | 52-71-11 | D05076P | | 27 | | | | D05078P | | 27 | | 050-099 |
| 203B | 24 | | PL | C | 68-0 | 52-71-11 | D05076P | | 27 | | | | D05078P | | 27 | | 150-199, 275-299 |
| 203R | 24 | | PL | C | 0-0 | 52-71-11 | D05076P | | 26 | | | | D05078P | | 26 | | ALL |
| 204B | 24 | | PL | D | 57-9 | 52-71-11 | D05076P | | 29 | | | | D05078P | | 29 | | 050-099 |
| 204B | 24 | | PL | D | 68-0 | 52-71-11 | D05076P | | 29 | | | | D05078P | | 29 | | 150-199, 275-299 |
| 204R | 24 | | PL | D | 0-0 | 52-71-11 | D05076P | | 28 | | | | D05078P | | 28 | | ALL |
| 205B | 24 | | PL | E | 53-2 | 52-71-12 | D05076P | | 31 | | | | SP00694 | | 9 | | 050-099 |
| 205B | 24 | | PL | E | 60-6 | 52-71-12 | D05076P | | 31 | | | | SP00694 | | 9 | | 150-199, 275-299 |
| 205R | 24 | | PL | E | 0-0 | 52-71-12 | D05076P | | 30 | | | | SP00692 | | 9 | | ALL |
| 206B | 24 | | PL | F | 57-9 | 52-71-11 | D05076P | | 33 | | | | D05078P | | 33 | | 050-099 |
| 206B | 24 | | PL | F | 68-0 | 52-71-11 | D05076P | | 33 | | | | D05078P | | 33 | | 150-199, 275-299 |
| 206R | 24 | | PL | F | 0-0 | 52-71-11 | D05076P | | 32 | | | | D05078P | | 32 | | ALL |
| 207B | 24 | | PL | G | 57-9 | 52-71-11 | D05076P | | 35 | | | | D05078P | | 35 | | 050-099 |
| 207B | 24 | | PL | G | 68-0 | 52-71-11 | D05076P | | 35 | | | | D05078P | | 35 | | 150-199, 275-299 |
| 207R | 24 | | PL | G | 0-0 | 52-71-11 | D05076P | | 34 | | | | D05078P | | 34 | | ALL |
| 212B | 24 | | PL | M | 63-4 | 52-71-12 | D05076P | | 39 | | | | SP02672 | | 9 | | 150-199, 275-299 |
| 212R | 24 | | PL | M | 0-0 | 52-71-12 | D05076P | | 38 | | | | SP02670 | | 9 | | 150-199, 275-299 |
| 601 | 20 | | PA | | 1-6 | 33-51-17 | D13254 | | C | | | | D13264 | | A | | 050-099 |
| 601 | 20 | | PA | | 2-5 | 33-51-17 | D13254 | | C | | | | D13264 | | A | | 150-199 |
| 602 | 20 | | PA | | 1-6 | 33-51-17 | D13254 | | B | | | | D13264 | | B | | 050-099 |
| 602 | 20 | | PA | | 2-5 | 33-51-17 | D13254 | | B | | | | D13264 | | B | | 150-199 |
| 603 | 20 | | PA | | 1-6 | 33-51-17 | D13254 | | F | | | | D13264 | | C | | 050-099 |
| 603 | 20 | | PA | | 2-5 | 33-51-17 | D13254 | | F | | | | D13264 | | C | | 150-199 |
| 604 | 20 | | PA | | 1-6 | 33-51-17 | D13254 | | E | | | | D13264 | | D | | 050-099 |
| 604 | 20 | | PA | | 2-5 | 33-51-17 | D13254 | | E | | | | D13264 | | D | | 150-199 |
| 605 | 20 | | PA | | 1-11 | 33-51-17 | D13254 | | D | | | | GD05572 | | D.. | E | 050-099 |
| 605 | 20 | | PA | | 2-11 | 33-51-17 | D13254 | | D | | | | GD05508 | | D.. | E | 150-199 |
| 606 | 20 | | PA | | 40-2 | 33-51-17 | D13254 | | L | | | | SM00028 | | S | | 050-099 |
| 606 | 22 | | PA | | 43-7 | 33-51-17 | D13254 | | L | | | | SM00028 | | S | | 150-199 |
| 607 | 20 | | PA | | 40-2 | 33-51-17 | D13254 | | K | | | | SM00011 | | S | | 050-099 |
| 607 | 22 | | PA | | 43-7 | 33-51-17 | D13254 | | K | | | | SM00011 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0784 | 286T0784 | | | WING ILLUMINATION LIGHTS, EMERGENCY LIGHTS (continued) | | | | | | | | | | | | | |
| 608 | 20 | | PA | 40-2 | 33-51-17 | D13254 | | A | | | | | SM00024 | | S | | 050-099 |
| 608 | 20 | | PA | 43-7 | 33-51-17 | D13254 | | A | | | | | SM00024 | | S | | 150-199 |
| 610 | 20 | | PA | 2-5 | 33-51-14 | D13206 | | C | | | | | SM00016 | | S | | 050-099 |
| 610 | 20 | | PA | 1-7 | 33-51-14 | D13206 | | C | | | | | SM00016 | | S | | 150-199 |
| 611 | 20 | | PA | 2-5 | 33-51-14 | D13206 | | B | | | | | SM00017 | | S | | 050-099 |
| 611 | 20 | | PA | 1-7 | 33-51-14 | D13206 | | B | | | | | SM00017 | | S | | 150-199 |
| 612 | 20 | | PA | 2-5 | 33-51-14 | D13206 | | F | | | | | SM00018 | | S | | 050-099 |
| 612 | 20 | | PA | 1-7 | 33-51-14 | D13206 | | F | | | | | SM00018 | | S | | 150-199 |
| 613 | 20 | | PA | 2-5 | 33-51-14 | D13206 | | E | | | | | SM00019 | | S | | 050-099 |
| 613 | 20 | | PA | 1-7 | 33-51-14 | D13206 | | E | | | | | SM00019 | | S | | 150-199 |
| 614 | 20 | | PA | 2-0 | 33-51-14 | D13206 | | D | | | | | GD05668 | D.. | E | | 050-099 |
| 614 | 20 | | PA | 2-1 | 33-51-14 | D13206 | | D | | | | | GD05672 | D.. | E | | 150-199 |
| 615 | 22 | | PA | 1-11 | 33-51-14 | D13206 | | L | | | | | SM00028 | | S | | 050-099 |
| 615 | 22 | | PA | 2-0 | 33-51-14 | D13206 | | L | | | | | SM00028 | | S | | 150-199 |
| 616 | 22 | | PA | 1-11 | 33-51-14 | D13206 | | K | | | | | SM00011 | | S | | 050-099 |
| 616 | 22 | | PA | 2-0 | 33-51-14 | D13206 | | K | | | | | SM00011 | | S | | 150-199 |
| 617 | 20 | | PA | 1-11 | 33-51-14 | D13206 | | A | | | | | SM00024 | | S | | 050-099 |
| 617 | 20 | | PA | 2-0 | 33-51-14 | D13206 | | A | | | | | SM00024 | | S | | 150-199 |
| 626 | 20 | | PA | 2-6 | 33-51-17 | D13258 | | A | | | | | SM00016 | | S | | 050-099 |
| 626 | 20 | | PA | 1-3 | 33-51-17 | D13258 | | A | | | | | SM00016 | | S | | 150-199 |
| 627 | 20 | | PA | 2-6 | 33-51-17 | D13258 | | B | | | | | SM00017 | | S | | 050-099 |
| 627 | 20 | | PA | 1-3 | 33-51-17 | D13258 | | B | | | | | SM00017 | | S | | 150-199 |
| 628 | 20 | | PA | 2-6 | 33-51-17 | D13258 | | C | | | | | SM00018 | | S | | 050-099 |
| 628 | 20 | | PA | 1-3 | 33-51-17 | D13258 | | C | | | | | SM00018 | | S | | 150-199 |
| 629 | 20 | | PA | 2-6 | 33-51-17 | D13258 | | D | | | | | SM00019 | | S | | 050-099 |
| 629 | 20 | | PA | 1-3 | 33-51-17 | D13258 | | D | | | | | SM00019 | | S | | 150-199 |
| 638 | 20 | | PA | 21-10 | 33-51-11 | D05076P | | 4 | | | | | SM00024 | | S | | 050-099 |
| 638 | 20 | | PA | 23-7 | 33-51-11 | D05076P | | 4 | | | | | SM00024 | | S | | 150-199 |
| 639 | 22 | | PA | 21-10 | 33-51-11 | D05076P | | 5 | | | | | SM00028 | | S | | 050-099 |
| 639 | 22 | | PA | 23-7 | 33-51-11 | D05076P | | 5 | | | | | SM00028 | | S | | 150-199 |
| 656 | 20 | | PA | 38-10 | 33-51-17 | SM00016 | | | S | | | | SM00035 | | S | | 050-099 |
| 656 | 20 | | PA | 44-1 | 33-51-17 | SM00035 | | | S | | | | SM00016 | | S | | 150-199 |
| 657 | 20 | | PA | 38-10 | 33-51-17 | SM00017 | | | S | | | | SM00034 | | S | | 050-099 |
| 657 | 20 | | PA | 44-1 | 33-51-17 | SM00034 | | | S | | | | SM00017 | | S | | 150-199 |
| 658 | 20 | | PA | 21-6 | 33-51-17 | SM00034 | | | S | | | | D13520 | B | | | 150-199 |
| 659 | 20 | | PA | 21-6 | 33-51-17 | SM00035 | | | S | | | | D13520 | A | | | 150-199 |
| 660 | 20 | | PA | 6-5 | 33-51-17 | D13522 | | B | | | | | SM00034 | | S | | 050-099 |
| 660 | 20 | | PA | 8-10 | 33-51-17 | SM00034 | | | S | | | | D13522 | B | | | 150-199 |
| 661 | 20 | | PA | 6-5 | 33-51-17 | D13522 | | A | | | | | SM00035 | | S | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0784 | 286T0784 | | | WING ILLUMINATION LIGHTS, EMERGENCY LIGHTS (continued) | | | | | | | | | | | |
| 661 | 20 | | PA | | 8-10 | 33-51-17 | SM00035 | | | | S | | | | 150-199 |
| 662 | 20 | | PA | | 7-6 | 33-51-17 | SM00034 | | | | S | | | | 050-099 |
| 662 | 20 | | PA | | 1-11 | 33-51-17 | SM00034 | | | | S | | | | 150-199 |
| 663 | 20 | | PA | | 7-6 | 33-51-17 | SM00035 | | | | S | | | | 050-099 |
| 663 | 20 | | PA | | 1-11 | 33-51-17 | SM00035 | | | | S | | | | 150-199 |
| 664 | 20 | | PA | | 6-0 | 33-51-17 | D13524 | | B | | S | | | | 050-099 |
| 664 | 20 | | PA | | 3-6 | 33-51-17 | D13524 | | B | | S | | | | 150-199 |
| 665 | 20 | | PA | | 6-0 | 33-51-17 | D13524 | | A | | S | | | | 050-099 |
| 665 | 20 | | PA | | 3-6 | 33-51-17 | D13524 | | A | | S | | | | 150-199 |
| 666 | 20 | | PA | | 9-1 | 33-51-17 | D13526 | | B | | S | | | | 050-099 |
| 666 | 20 | | PA | | 7-2 | 33-51-17 | D13526 | | B | | S | | | | 150-199 |
| 667 | 20 | | PA | | 9-1 | 33-51-17 | D13526 | | A | | S | | | | 050-099 |
| 667 | 20 | | PA | | 7-2 | 33-51-17 | D13526 | | A | | S | | | | 150-199 |
| 668 | 20 | | PA | | 5-0 | 33-51-17 | D12072 | | B | | S | | | | 150-199 |
| 669 | 20 | | PA | | 5-0 | 33-51-17 | D12072 | | A | | S | | | | 150-199 |
| 670 | 20 | | PA | | 7-6 | 33-51-17 | D12074 | | B | | S | | | | 050-099 |
| 670 | 20 | | PA | | 2-10 | 33-51-17 | D12074 | | B | | S | | | | 150-199 |
| 671 | 20 | | PA | | 7-6 | 33-51-17 | D12074 | | A | | S | | | | 050-099 |
| 671 | 20 | | PA | | 2-10 | 33-51-17 | D12074 | | A | | S | | | | 150-199 |
| 672 | 20 | | PA | | 38-10 | 33-51-17 | SM00019 | | | | S | | | | 050-099 |
| 672 | 20 | | PA | | 44-1 | 33-51-17 | SM00019 | | | | S | | | | 150-199 |
| 673 | 20 | | PA | | 38-10 | 33-51-17 | SM00018 | | | | S | | | | 050-099 |
| 673 | 20 | | PA | | 44-1 | 33-51-17 | SM00018 | | | | S | | | | 150-199 |
| 674 | 20 | | PA | | 21-6 | 33-51-17 | SM00038 | | | | S | | | | 150-199 |
| 675 | 20 | | PA | | 21-6 | 33-51-17 | SM00039 | | | | S | | D | | 150-199 |
| 676 | 20 | | PA | | 3-11 | 33-51-17 | SM00038 | | | | S | | C | | 150-199 |
| 677 | 20 | | PA | | 3-11 | 33-51-17 | SM00039 | | | | S | | | | 150-199 |
| 678 | 20 | | PA | | 7-6 | 33-51-17 | SM00040 | | | | S | | | | 050-099 |
| 678 | 20 | | PA | | 1-6 | 33-51-17 | SM00040 | | | | S | | | | 150-199 |
| 679 | 20 | | PA | | 9-0 | 33-51-17 | SM00040 | | | | S | | D | | 150-199 |
| 680 | 20 | | PA | | 9-0 | 33-51-17 | SM00041 | | | | S | | C | | 150-199 |
| 681 | 20 | | PA | | 6-5 | 33-51-17 | D13522 | | D | | S | | | | 050-099 |
| 681 | 20 | | PA | | 5-0 | 33-51-17 | SM00040 | | | | S | | D | | 150-199 |
| 682 | 20 | | PA | | 6-5 | 33-51-17 | D13522 | | C | | S | | | | 050-099 |
| 682 | 20 | | PA | | 5-0 | 33-51-17 | SM00041 | | | | S | | C | | 150-199 |
| 683 | 20 | | PA | | 7-6 | 33-51-17 | SM00041 | | | | S | | | | 050-099 |
| 683 | 20 | | PA | | 1-6 | 33-51-17 | SM00041 | | | | S | | | | 150-199 |
| 684 | 20 | | PA | | 7-6 | 33-51-17 | D12074 | | D | | S | | | | 050-099 |
| 684 | 20 | | PA | | 8-1 | 33-51-17 | SM00042 | | | | S | | D | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0784 | 286T0784 | | | WING ILLUMINATION LIGHTS, EMERGENCY LIGHTS (continued) | | | | | | | | | | | |
| 685 | 20 | | PA | | 7-6 | 33-51-17 | D12074 | | C | | SM00043 | | S | | 050-099 |
| 685 | 20 | | PA | | 8-1 | 33-51-17 | SM00043 | | S | | D12074 | | C | | 150-199 |
| 686 | 20 | | PA | | 6-0 | 33-51-17 | D13524 | | D | | SM00042 | | S | | 050-099 |
| 686 | 20 | | PA | | 8-8 | 33-51-17 | SM00042 | | S | | D13524 | | D | | 150-199 |
| 687 | 20 | | PA | | 6-0 | 33-51-17 | D13524 | | C | | SM00043 | | S | | 050-099 |
| 687 | 20 | | PA | | 8-8 | 33-51-17 | SM00043 | | S | | D13524 | | C | | 150-199 |
| 688 | 20 | | PA | | 9-1 | 33-51-17 | D13526 | | D | | SM00042 | | S | | 050-099 |
| 688 | 20 | | PA | | 11-11 | 33-51-17 | SM00042 | | S | | D13526 | | D | | 150-199 |
| 689 | 20 | | PA | | 9-1 | 33-51-17 | D13526 | | C | | SM00043 | | S | | 050-099 |
| 689 | 20 | | PA | | 11-11 | 33-51-17 | SM00043 | | S | | D13526 | | C | | 150-199 |
| 801 | 20 | | PA | | 4-9 | 33-22-21 | D12088P | | = 1 | | GD04876 | | A.. | 2 | 150-199 |
| 814 | 20 | | PA | | 57-9 | SPARE | D05076P | | 18 | | D05078P | | 31 | | 050-099 |
| 814 | 20 | | PA | | 68-0 | SPARE | D05076P | | 18 | | D05078P | | 31 | | 150-199, 275-299 |
| A-A | | | | | 0-0 | 52-71-12 | SP00692 | | | 9 | S00192 | | RED | | ALL |
| A-B | | | | | 0-0 | 52-71-12 | SP00694 | | | 9 | S00192 | | BLU | | ALL |
| B-A | | | | | 0-0 | 52-71-12 | S00216 | | RED | | SP02670 | | | 9 | 150-199, 275-299 |
| B-B | | | | | 0-0 | 52-71-12 | S00216 | | BLU | | SP02672 | | | 9 | 150-199, 275-299 |
| C-A | | | | | 0-0 | 33-51-21 | D06322J | | = 1 | | L00397 | | GND | | ALL |
| C-B | | | | | 0-0 | 33-51-21 | D06320P | | = 1 | | L00397 | | PWR | | ALL |
| W0785 | 286T0785 | | | EXIT. IDENTIFIERS JUMPER BUNDLE | | | | | | | | | | | |
| 001 | 20 | | PA | | 2-0 | 33-51-14 | D02569 | | C | | D02569 | | D | | 050-099, 150-199 |
| 002 | 20 | | PA | | 2-0 | 33-51-14 | D02569 | | B | | D02571 | | = 1 | | 050-099, 150-199 |
| 003 | 20 | | PA | | 2-0 | 33-51-14 | D02569 | | A | | D02573 | | = 1 | | 050-099, 150-199 |
| W0786 | 286T0786 | | | R MID EMER LTG | | | | | | | | | | | |
| 001 | 20 | | PA | | 40-11 | 33-41-11 | D05082P | | 3 | | L00060 | | 115V | E | 050-099 |
| 001 | 18 | | PA | | 43-8 | 33-41-11 | D05082P | | 3 | DL | L00060 | | 115V | E | 150-199, 275-299 |
| 002 | 14 | | PA | | 2-8 | 33-41-11 | L00060 | | RTN | E | GD01440 | | A.. | E | 050-099 |
| 002 | 14 | | PA | | 3-2 | 33-41-11 | L00060 | | RTN | E | GD05086 | | A.. | E | 150-199, 275-299 |
| 003 | 20 | | PA | | 14-5 | 33-51-11 | SP02504 | | | S | D05082P | | 14 | | 050-099 |
| 003 | 20 | | PA | | 14-7 | 33-51-11 | SP02504 | | | S | D05082P | | 14 | | 150-199, 275-299 |
| 029 | 20 | | PA | | 1-6 | 33-51-21 | D01122 | | 7 | | GD05662 | | S.. | E | 050-099, 150-199 |
| 029 | 20 | | PA | | 3-1 | 33-51-21 | D01122 | | 7 | | GD03652 | | S.. | E | 275-299 |
| 030 | 20 | | PA | | 1-6 | 33-51-21 | D01122 | | 1 | | GD05660 | | D.. | E | 050-099, 150-199 |
| 030 | 20 | | PA | | 3-1 | 33-51-21 | D01122 | | 1 | | GD03654 | | D.. | E | 275-299 |
| 031 | 22 | | PA | | 33-9 | 33-51-21 | D01122 | | 8 | | D05082P | | 6 | | 050-099 |
| 031 | 22 | | PA | | 33-7 | 33-51-21 | D01122 | | 8 | | D05082P | | 6 | | 150-199 |
| 031 | 22 | | PA | | 23-5 | 33-51-21 | D01122 | | 8 | | D05082P | | 6 | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0780
Page 12
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0786 | 286T0786 | | | R MID EMER LTG (continued) | | | | | | | | | | | | | |
| 032 | 22 | | PA | 33-9 | 33-51-21 | D01122 | | 2 | | | | | D05082P | 7 | | | 050-099 |
| 032 | 22 | | PA | 33-7 | 33-51-21 | D01122 | | 2 | | | | | D05082P | 7 | | | 150-199 |
| 032 | 22 | | PA | 23-5 | 33-51-21 | D01122 | | 2 | | | | | D05082P | 7 | | | 275-299 |
| 033 | 22 | | PA | 24-7 | 33-51-21 | D01122 | | 3 | | | | | SP02504 | | S | | 050-099 |
| 033 | 22 | | PA | 24-9 | 33-51-21 | D01122 | | 3 | | | | | SP02504 | | S | | 150-199 |
| 033 | 22 | | PA | 14-7 | 33-51-21 | D01122 | | 3 | | | | | SP02504 | | S | | 275-299 |
| 034 | 22 | | PA | 8-10 | 33-51-21 | D01122 | | 4 | | | | | SM00013 | | S | | 050-099 |
| 034 | 22 | | PA | 1-6 | 33-51-21 | D01122 | | 4 | | | | | SM00013 | | S | | 150-199 |
| 034 | 22 | | PA | 8-7 | 33-51-21 | D01122 | | 4 | | | | | SM00013 | | S | | 275-299 |
| 035 | 22 | | PA | 2-0 | 33-51-21 | D01122 | | 6 | | | | | D01122 | 5 | | | ALL |
| 036 | 16 | | PA | 44-5 | 33-51-21 | D01122 | | 9 | FM | | | | D06324J | =1 | | | 050-099 |
| 036 | 16 | | PA | 44-0 | 33-51-21 | D01122 | | 9 | FM | | | | D06324J | =1 | | | 150-199 |
| 036 | 16 | | PA | 33-10 | 33-51-21 | D01122 | | 9 | FM | | | | D06324J | =1 | | | 275-299 |
| 037 | 16 | | PA | 4-10 | 33-51-21 | D06326P | | =1 | | | | | GD04730 | D.. | E | | ALL |
| 038 | 20 | | PA | 1-6 | 33-51-21 | D01122 | | 10 | | | | | SM00002 | | S | | ALL |
| 039 | 14 | | PA | 3-0 | 33-51-21 | L00394 | | 2 | D | | | | GD02494 | D.. | E | | 050-099 |
| 039 | 14 | | PA | 2-3 | 33-51-21 | L00394 | | 2 | D | | | | GD04640 | D.. | E | | 150-199, 275-299 |
| 040 | 14 | | PA | 50-8 | 33-51-21 | L00394 | | 1 | D | | | | SM00002 | | S | | 050-099 |
| 040 | 14 | | PA | 57-8 | 33-51-21 | L00394 | | 1 | D | | | | SM00002 | | S | | 150-199 |
| 040 | 14 | | PA | 69-4 | 33-51-21 | L00394 | | 1 | D | | | | SM00002 | | S | | 275-299 |
| 041 | 18 | | PA | 30-11 | 25-65-11 | D01082 | | 15 | DK | | | | D06402P | 7 | | | 050-099 |
| 041 | 18 | | PA | 36-4 | 25-65-11 | D01082 | | 15 | DK | | | | D06404P | 7 | DK | | 150-199 |
| 041 | 18 | | PA | 32-1 | 25-65-11 | D01082 | | 15 | DK | | | | D06404P | 7 | DK | | 275-299 |
| 042 | 18 | | PA | 12-7 | 25-65-12 | D01082 | | 13 | DK | | | | D06406P | 4 | | | 050-099 |
| 042 | 18 | | PA | 26-2 | 25-65-12 | D01082 | | 13 | DK | | | | D06408P | 4 | DK | | 150-199 |
| 042 | 18 | | PA | 21-11 | 25-65-12 | D01082 | | 13 | DK | | | | D06408P | 4 | DK | | 275-299 |
| 043 | 22 | | PA | 1-0 | 25-65-12 | D01082 | | 24 | | | | | D01082 | 18 | | | ALL |
| 044 | 22 | | PA | 1-0 | 25-65-12 | D01082 | | 5 | | | | | D01082 | 6 | | | ALL |
| 045 | 20 | | PA | 3-4 | 25-65-12 | D01082 | | 7 | | | | | GD03624 | S.. | E | | 050-099 |
| 045 | 20 | | PA | 2-3 | 25-65-12 | D01082 | | 7 | | | | | GD05700 | S.. | E | | 150-199 |
| 045 | 20 | | PA | 3-4 | 25-65-12 | D01082 | | 7 | | | | | GD04642 | S.. | E | | 275-299 |
| 046 | 18 | | PA | 3-4 | 25-65-12 | D01082 | | 1 | DK | | | | GD03626 | D.. | E | | 050-099 |
| 046 | 18 | | PA | 1-7 | 25-65-12 | D01082 | | 1 | DK | | | | GD05702 | D.. | E | | 150-199 |
| 046 | 18 | | PA | 2-2 | 25-65-12 | D01082 | | 1 | DK | | | | GD04644 | D.. | E | | 275-299 |
| 047 | 22 | | PA | 64-7 | 25-65-12 | D01082 | | 2 | | | | | D05082P | 12 | | | 050-099 |
| 047 | 22 | | PA | 83-10 | 25-65-12 | D01082 | | 2 | | | | | D05082P | 12 | | | 150-199 |
| 047 | 22 | | PA | 79-6 | 25-65-12 | D01082 | | 2 | | | | | D05082P | 12 | | | 275-299 |
| 048 | 18 | | PA | 30-2 | 25-65-12 | D01086 | | 15 | DK | | | | D06406P | 7 | | | 050-099 |
| 048 | 18 | | PA | 34-10 | 25-65-12 | D01086 | | 15 | DK | | | | D06408P | 7 | DK | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0786 | 286T0786 | | | R MID EMER LTG (continued) | | | | | | | | | | | | |
| 048 | 18 | PA | | 32-6 | 25-65-12 | D01086 | | 15 | DK | | D06408P | 7 | DK | | 275-299 | |
| 049 | 18 | PA | | 11-9 | 25-65-11 | D01086 | | 13 | DK | | D06402P | 4 | | | 050-099 | |
| 049 | 18 | PA | | 45-0 | 25-65-11 | D01086 | | 13 | DK | | D06404P | 4 | DK | | 150-199 | |
| 049 | 18 | PA | | 22-0 | 25-65-11 | D01086 | | 13 | DK | | D06404P | 4 | DK | | 275-299 | |
| 050 | 22 | PA | | 1-0 | 25-65-11 | D01086 | | 18 | | | D01086 | 24 | | | ALL | |
| 051 | 22 | PA | | 1-0 | 25-65-11 | D01086 | | 5 | | | D01086 | 6 | | | ALL | |
| 052 | 20 | PA | | 1-11 | 25-65-11 | D01086 | | 7 | | | GD03628 | S.. | E | | 050-099 | |
| 052 | 20 | PA | | 1-9 | 25-65-11 | D01086 | | 7 | | | GD05686 | S.. | E | | 150-199 | |
| 052 | 20 | PA | | 3-6 | 25-65-11 | D01086 | | 7 | | | GD04646 | S.. | E | | 275-299 | |
| 053 | 18 | PA | | 1-11 | 25-65-11 | D01086 | | 1 | DK | | GD03630 | D.. | E | | 050-099 | |
| 053 | 18 | PA | | 2-6 | 25-65-11 | D01086 | | 1 | DK | | GD05688 | D.. | E | | 150-199 | |
| 053 | 18 | PA | | 2-1 | 25-65-11 | D01086 | | 1 | DK | | GD04648 | D.. | E | | 275-299 | |
| 054 | 22 | PA | | 73-4 | 25-65-11 | D01086 | | 2 | | | D05082P | 13 | | | 050-099 | |
| 054 | 22 | PA | | 92-6 | 25-65-11 | D01086 | | 2 | | | D05082P | 13 | | | 150-199 | |
| 054 | 22 | PA | | 90-1 | 25-65-11 | D01086 | | 2 | | | D05082P | 13 | | | 275-299 | |
| 056 | 22 | PA | | 2-0 | 33-51-21 | D01122 | | 20 | | | D01122 | 24 | | | 050-099, 280-299 | |
| 056 | 22 | PA | | 0-7 | 33-51-21 | D01122 | | 20 | | | D01122 | 24 | | | 150-199, 275-278 | |
| 057 | 14 | PA | | 2-8 | 33-41-11 | L00060 | | | GND | E | GD04180 | S.. | E | | 050-099 | |
| 057 | 14 | PA | | 2-8 | 33-41-11 | L00060 | | | GND | E | GD05088 | S.. | E | | 150-199, 275-299 | |
| 058 | 20 | PA | | 3-4 | 25-65-12 | D01082 | | 4 | | | GD03626 | D.. | E | | 050-099 | |
| 058 | 20 | PA | | 1-7 | 25-65-12 | D01082 | | 4 | | | GD05702 | D.. | E | | 150-199 | |
| 058 | 20 | PA | | 2-2 | 25-65-12 | D01082 | | 4 | | | GD04644 | D.. | E | | 275-299 | |
| 059 | 20 | PA | | 3-4 | 25-65-12 | D01082 | | 3 | | | GD03626 | D.. | E | | 050-099 | |
| 059 | 20 | PA | | 1-7 | 25-65-12 | D01082 | | 3 | | | GD05702 | D.. | E | | 150-199 | |
| 059 | 20 | PA | | 2-2 | 25-65-12 | D01082 | | 3 | | | GD04644 | D.. | E | | 275-299 | |
| 060 | 20 | PA | | 1-11 | 25-65-11 | D01086 | | 4 | | | GD03630 | D.. | E | | 050-099 | |
| 060 | 20 | PA | | 2-6 | 25-65-11 | D01086 | | 4 | | | GD05688 | D.. | E | | 150-199 | |
| 060 | 20 | PA | | 2-1 | 25-65-11 | D01086 | | 4 | | | GD04648 | D.. | E | | 275-299 | |
| 061 | 20 | PA | | 1-11 | 25-65-11 | D01086 | | 3 | | | GD03630 | D.. | E | | 050-099 | |
| 061 | 20 | PA | | 2-6 | 25-65-11 | D01086 | | 3 | | | GD05688 | D.. | E | | 150-199 | |
| 061 | 20 | PA | | 2-1 | 25-65-11 | D01086 | | 3 | | | GD04648 | D.. | E | | 275-299 | |
| 062 | 20 | PA | | 1-6 | 33-51-21 | D01122 | | 11 | | | SM00005 | | S | | ALL | |
| 063 | 20 | PA | | 1-6 | 33-51-21 | D01122 | | 12 | | | SM00006 | | S | | ALL | |
| 064 | 14 | PA | | 56-9 | 33-51-21 | L00643 | | 1 | D | | SM00006 | | S | | 050-099 | |
| 064 | 14 | PA | | 66-5 | 33-51-21 | L00643 | | 1 | D | | SM00006 | | S | | 150-199 | |
| 064 | 14 | PA | | 78-1 | 33-51-21 | L00643 | | 1 | D | | SM00006 | | S | | 275-299 | |
| 065 | 14 | PA | | 3-1 | 33-51-21 | L00643 | | 2 | D | | GD04210 | D.. | E | | ALL | |
| 066 | 14 | PA | | 64-8 | 33-51-21 | L00390 | | 1 | D | | SM00005 | | S | | 050-099 | |
| 066 | 14 | PA | | 73-10 | 33-51-21 | L00390 | | 1 | D | | SM00005 | | S | | 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0786 | 286T0786 | | | R MID EMER LTG (continued) | | | | | | | | | | | | | |
| 066 | 14 | | PA | 85-7 | 33-51-21 | L00390 | | 1 | D | | | | SM00005 | | | S | 275-299 |
| 067 | 14 | | PA | 2-6 | 33-51-21 | L00390 | | 2 | D | | | | GD04220 | D.. | E | | 050-099 |
| 067 | 14 | | PA | 2-2 | 33-51-21 | L00390 | | 2 | D | | | | GD04220 | D.. | E | | 150-199, 275-299 |
| 068 | 22 | | PA | 107-4 | 33-51-21 | D02610 | | 8 | | | | | D05082P | 22 | | | 050-099 |
| 068 | 22 | | PA | 125-4 | 33-51-21 | D02610 | | 8 | | | | | D05082P | 22 | | | 150-157, 275-299 |
| 068 | 22 | | PA | 128-3 | 33-51-21 | D02610 | | 8 | | | | | D05082P | 22 | | | 162-199 |
| 069 | 20 | | PA | 1-6 | 33-51-21 | D02610 | | 11 | | | | | SM00012 | | | S | ALL |
| 070 | 22 | | PA | 0-7 | 33-51-21 | D02610 | | 20 | | | | | D02610 | 24 | | | 050-099 |
| 070 | 22 | | PA | 2-0 | 33-51-21 | D02610 | | 20 | | | | | D02610 | 24 | | | 150-199, 275-299 |
| 071 | 20 | | PA | 2-7 | 33-51-21 | D02610 | | 1 | | | | | GD02594 | D.. | E | | 050-099 |
| 071 | 20 | | PA | 1-9 | 33-51-21 | D02610 | | 1 | | | | | GD02708 | D.. | E | | 150-157, 275-299 |
| 071 | 20 | | PA | 2-1 | 33-51-21 | D02610 | | 1 | | | | | GD02594 | D.. | E | | 162-199 |
| 072 | 20 | | PA | 107-4 | 33-51-21 | D02610 | | 2 | | | | | D05082P | 23 | | | 050-099 |
| 072 | 20 | | PA | 125-4 | 33-51-21 | D02610 | | 2 | | | | | D05082P | 23 | | | 150-157, 275-299 |
| 072 | 20 | | PA | 128-3 | 33-51-21 | D02610 | | 2 | | | | | D05082P | 23 | | | 162-199 |
| 073 | 22 | | PA | 17-8 | 33-51-21 | D02610 | | 3 | | | | | SP02506 | | | S | 050-099, 162-199 |
| 073 | 22 | | PA | 14-8 | 33-51-21 | D02610 | | 3 | | | | | SP02506 | | | S | 150-157, 275-299 |
| 074 | 22 | | PA | 86-0 | 33-51-21 | D02610 | | 4 | | | | | SM00013 | | | S | 050-099 |
| 074 | 22 | | PA | 110-11 | 33-51-21 | D02610 | | 4 | | | | | SM00013 | | | S | 150-157 |
| 074 | 22 | | PA | 113-11 | 33-51-21 | D02610 | | 4 | | | | | SM00013 | | | S | 162-199 |
| 074 | 22 | | PA | 116-0 | 33-51-21 | D02610 | | 4 | | | | | SM00013 | | | S | 275-299 |
| 075 | 22 | | PA | 0-7 | 33-51-21 | D02610 | | 5 | | | | | D02610 | 6 | | | 050-099 |
| 075 | 22 | | PA | 2-0 | 33-51-21 | D02610 | | 5 | | | | | D02610 | 6 | | | 150-199, 275-299 |
| 077 | 20 | | PA | 2-7 | 33-51-21 | D02610 | | 7 | | | | | GD02596 | S.. | E | | 050-099 |
| 077 | 20 | | PA | 1-9 | 33-51-21 | D02610 | | 7 | | | | | GD02710 | S.. | E | | 150-157, 275-299 |
| 077 | 20 | | PA | 2-1 | 33-51-21 | D02610 | | 7 | | | | | GD02596 | S.. | E | | 162-199 |
| 078 | 14 | | PA | 35-4 | 33-51-21 | D06316J | | =1 | FO | | | | SM00012 | | | S | 050-099 |
| 078 | 14 | | PA | 36-9 | 33-51-21 | D06316J | | =1 | FO | | | | SM00012 | | | S | 150-157, 275-299 |
| 078 | 14 | | PA | 35-5 | 33-51-21 | D06316J | | =1 | FO | | | | SM00012 | | | S | 162-199 |
| 079 | 16 | | PA | 3-9 | 33-51-21 | D06318P | | =1 | | | | | GD02706 | D.. | E | | 050-099 |
| 079 | 16 | | PA | 3-10 | 33-51-21 | D06318P | | =1 | | | | | GD02706 | D.. | E | | 150-199, 275-299 |
| 080 | 20 | | PA | 1-6 | 33-51-21 | D02610 | | 10 | | | | | SM00011 | | | S | ALL |
| 081 | 20 | | PA | 27-7 | 33-51-21 | D02610 | | 12 | | | | | L00644 | 1 | D | | 050-099 |
| 081 | 20 | | PA | 42-6 | 33-51-21 | D02610 | | 12 | | | | | L00644 | 1 | D | | 150-157, 275-299 |
| 081 | 20 | | PA | 45-6 | 33-51-21 | D02610 | | 12 | | | | | L00644 | 1 | D | | 162-199 |
| 082 | 20 | | PA | 4-4 | 33-51-21 | L00644 | | 2 | D | | | | GD03076 | D.. | E | | 050-099 |
| 082 | 20 | | PA | 6-1 | 33-51-21 | L00644 | | 2 | D | | | | GD04484 | D.. | E | | 150-199, 275-299 |
| 084 | 12 | | PA | 45-2 | 33-51-21 | L00391 | | 1 | D | | | | SM00011 | | | S | 050-099 |
| 084 | 12 | | PA | 48-7 | 33-51-21 | L00391 | | 1 | D | | | | SM00011 | | | S | 150-157, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|-------|------|------|---------|-------------|---|----|------------------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0786 | 286T0786 | | | R MID EMER LTG (continued) | | | | | | | | | | | | | | | |
| 084 | 12 | | PA | | 52-1 | 33-51-21 | L00391 | | 1 | D | | | | SM00011 | | S | | 162-199 | |
| 085 | 12 | | PA | | 7-10 | 33-51-21 | L00391 | | 2 | D | | | | GD04484 | D.. | E | | 050-099 | |
| 085 | 12 | | PA | | 2-2 | 33-51-21 | L00391 | | 2 | D | | | | GD04816 | D.. | E | | 150-199, 275-299 | |
| 089 | 22 | | PA | | 26-0 | 33-51-21 | D05082P | | 24 | | | | | SM00013 | | S | | 050-099 | |
| 089 | 22 | | PA | | 32-7 | 33-51-21 | D05082P | | 24 | | | | | SM00013 | | S | | 150-199 | |
| 089 | 22 | | PA | | 15-10 | 33-51-21 | D05082P | | 24 | | | | | SM00013 | | S | | 275-299 | |
| 091 | 20 | | PA | | 71-0 | 27-61-18 | D10500 | | 1 | | | | | D05082P | | | 19 | 050-099 | |
| 091 | 20 | | PA | | 81-5 | 27-61-18 | D10500 | | 1 | | | | | D05082P | | | 19 | 150-199, 275-299 | |
| 092 | 20 | | PA | | 2-9 | 27-61-18 | D10500 | | 2 | | | | | GD02546 | D.. | E | | 050-099 | |
| 092 | 20 | | PA | | 2-4 | 27-61-18 | D10500 | | 2 | | | | | GD04636 | D.. | E | | 150-199, 275-299 | |
| 093 | 16 | | PA | | 2-9 | 25-65-12 | D10502 | | 3 | FM | | | | GD02498 | D.. | E | | 050-099 | |
| 093 | 16 | | PA | | 2-3 | 25-65-12 | D10502 | | 3 | FM | | | | GD04638 | D.. | E | | 150-199, 275-299 | |
| 094 | 22 | | PA | | 71-0 | 25-65-11 | D10500 | | 4 | | | | | D05082P | | | 17 | 050-099 | |
| 094 | 22 | | PA | | 81-5 | 25-65-11 | D10500 | | 4 | | | | | D05082P | | | 17 | 150-199, 275-299 | |
| 095 | 22 | | PA | | 71-0 | 25-65-11 | D10500 | | 8 | | | | | D05082P | | | 18 | 050-099 | |
| 095 | 22 | | PA | | 81-5 | 25-65-11 | D10500 | | 8 | | | | | D05082P | | | 18 | 150-199, 275-299 | |
| 096 | 22 | | PA | | 71-0 | 25-65-11 | D10500 | | 13 | | | | | D05082P | | | 16 | 050-099 | |
| 096 | 22 | | PA | | 81-5 | 25-65-11 | D10500 | | 13 | | | | | D05082P | | | 16 | 150-199, 275-299 | |
| 097 | 20 | | PA | | 4-0 | 25-65-12 | D10502 | | 15 | | | | | D06406P | | | 3 | 050-099 | |
| 097 | 18 | | PA | | 16-2 | 25-65-12 | D10502 | | 15 | DK | | | | S00629 | | C | * | 6 | 150-199, 275-299 |
| 098 | 22 | | PA | | 4-0 | 25-65-12 | D10502 | | 16 | | | | | D06406P | | | 2 | 050-099 | |
| 098 | 22 | | PA | | 13-0 | 25-65-12 | D10502 | | 16 | | | | | D06408P | | | 2 | 150-199, 275-299 | |
| 099 | 22 | | PA | | 4-0 | 25-65-12 | D10502 | | 18 | | | | | D06406P | | | 1 | 050-099 | |
| 099 | 22 | | PA | | 13-0 | 25-65-12 | D10502 | | 18 | | | | | D06408P | | | 1 | 150-199, 275-299 | |
| 100 | 22 | | PA | | 4-0 | 25-65-12 | D10502 | | 20 | | | | | D06406P | | | 5 | 050-099 | |
| 100 | 22 | | PA | | 16-4 | 25-65-12 | D10502 | | 20 | | | | | D06406P | | | 5 | 150-199, 275-299 | |
| 101 | 20 | | PA | | 4-0 | 25-65-12 | D10502 | | 21 | | | | | D06406P | | | 8 | 050-099 | |
| 101 | 20 | | PA | | 13-0 | 25-65-12 | D10502 | | 21 | | | | | D06408P | | | 8 | 150-199, 275-299 | |
| 102 | 16 | | PA | | 10-11 | 25-65-12 | D10502 | | 22 | FM | | | | SP02566 | | S | | 050-099 | |
| 102 | 16 | | PA | | 10-0 | 25-65-12 | D10502 | | 22 | FM | | | | SP02566 | | S | | 150-199, 275-299 | |
| 103 | 16 | | PA | | 10-11 | 25-65-12 | D10502 | | 23 | FM | | | | SP02564 | | S | | 050-099 | |
| 103 | 16 | | PA | | 10-0 | 25-65-12 | D10502 | | 23 | FM | | | | SP02564 | | S | | 150-199, 275-299 | |
| 104 | 20 | | PA | | 4-0 | 25-65-12 | D10502 | | 24 | | | | | D06406P | | | 6 | 050-099 | |
| 104 | 20 | | PA | | 13-0 | 25-65-12 | D10502 | | 24 | | | | | D06408P | | | 6 | 150-199, 275-299 | |
| 105 | 20 | | PA | | 61-8 | 27-61-18 | D10502 | | 1 | | | | | D05082P | | | 20 | 050-099 | |
| 105 | 20 | | PA | | 70-7 | 27-61-18 | D10502 | | 1 | | | | | D05082P | | | 20 | 150-199, 275-299 | |
| 106 | 20 | | PA | | 2-9 | 27-61-18 | D10502 | | 2 | | | | | GD02498 | D.. | E | | 050-099 | |
| 106 | 20 | | PA | | 2-3 | 27-61-18 | D10502 | | 2 | | | | | GD04638 | D.. | E | | 150-199, 275-299 | |
| 107 | 16 | | PA | | 2-9 | 25-65-11 | D10500 | | 3 | FM | | | | GD02546 | D.. | E | | 050-099 | |

WIRE LIST
D280T132

91-21-11
Section W0780
Page 16
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0786 | 286T0786 | | | R MID EMER LTG (continued) | | | | | | | | | | | | | |
| 107 | 16 | | PA | 2-4 | 25-65-11 | D10500 | 3 | FM | | | | | GD04636 | D.. | E | | 150-199, 275-299 |
| 108 | 22 | | PA | 61-8 | 25-65-12 | D10502 | 4 | | | | | | D05082P | 9 | | | 050-099 |
| 108 | 22 | | PA | 70-7 | 25-65-12 | D10502 | 4 | | | | | | D05082P | 9 | | | 150-199, 275-299 |
| 109 | 22 | | PA | 61-8 | 25-65-12 | D10502 | 8 | | | | | | D05082P | 15 | | | 050-099 |
| 109 | 22 | | PA | 70-7 | 25-65-12 | D10502 | 8 | | | | | | D05082P | 15 | | | 150-199, 275-299 |
| 110 | 22 | | PA | 61-8 | 25-65-12 | D10502 | 13 | | | | | | D05082P | 8 | | | 050-099 |
| 110 | 22 | | PA | 70-7 | 25-65-12 | D10502 | 13 | | | | | | D05082P | 8 | | | 150-199, 275-299 |
| 111 | 20 | | PA | 3-9 | 25-65-11 | D10500 | 15 | | | | | | D06402P | 3 | | | 050-099 |
| 111 | 18 | | PA | 16-10 | 25-65-11 | D10500 | 15 | DK | | | | | S00630 | 6 | C | * | 150-199, 275-299 |
| 112 | 22 | | PA | 3-9 | 25-65-11 | D10500 | 16 | | | | | | D06402P | 2 | | | 050-099 |
| 112 | 22 | | PA | 13-5 | 25-65-11 | D10500 | 16 | | | | | | D06404P | 2 | | | 150-199, 275-299 |
| 113 | 22 | | PA | 3-9 | 25-65-11 | D10500 | 18 | | | | | | D06402P | 1 | | | 050-099 |
| 113 | 22 | | PA | 13-5 | 25-65-11 | D10500 | 18 | | | | | | D06404P | 1 | | | 150-199, 275-299 |
| 114 | 22 | | PA | 3-9 | 25-65-11 | D10500 | 20 | | | | | | D06402P | 5 | | | 050-099 |
| 114 | 22 | | PA | 17-1 | 25-65-11 | D10500 | 20 | | | | | | D06402P | 5 | | | 150-199, 275-299 |
| 115 | 20 | | PA | 3-9 | 25-65-11 | D10500 | 21 | | | | | | D06402P | 8 | | | 050-099 |
| 115 | 20 | | PA | 13-5 | 25-65-11 | D10500 | 21 | | | | | | D06404P | 8 | | | 150-199, 275-299 |
| 116 | 16 | | PA | 9-4 | 25-65-11 | D10500 | 22 | FM | | | | | SP02568 | | S | | 050-099 |
| 116 | 16 | | PA | 8-1 | 25-65-11 | D10500 | 22 | FM | | | | | SP02568 | | S | | 150-199, 275-299 |
| 117 | 16 | | PA | 49-2 | 25-65-11 | D10500 | 23 | FM | | | | | SP01638 | 9 | | | 050-099 |
| 117 | 16 | | PA | 43-1 | 25-65-11 | D10500 | 23 | FM | | | | | SP01638 | 9 | | | 150-199, 275-299 |
| 118 | 20 | | PA | 3-9 | 25-65-11 | D10500 | 24 | | | | | | D06402P | 6 | | | 050-099 |
| 118 | 20 | | PA | 13-5 | 25-65-11 | D10500 | 24 | | | | | | D06404P | 6 | | | 150-199, 275-299 |
| 127 | 18 | | PA | 14-9 | 25-65-11 | D06402P | 7 | | | | | | D06404P | 16 | DK | | 150-199, 275-299 |
| 128 | 18 | | PA | 14-9 | 25-65-11 | D06402P | 4 | | | | | | D06404P | 14 | DK | | 150-199, 275-299 |
| 130 | 18 | | PA | 14-9 | 25-65-11 | D06402P | 10 | | | | | | D06404P | 10 | DK | | 150-199, 275-299 |
| 131 | 20 | | PA | 12-6 | 25-65-11 | S00630 | 2 | C | | * | | | D06402P | 3 | | | 150-199, 275-299 |
| 132 | 20 | | PA | 1-0 | 25-65-11 | S00630 | 2 | C | | * | | | S00630 | 6 | C | * | 150-199, 275-299 |
| 133 | 22 | | PA | 17-1 | 25-65-11 | D06402P | 2 | | | | | | D10500 | 14 | | | 150-199, 275-299 |
| 135 | 22 | | PA | 12-6 | 25-65-11 | D06402P | 1 | | | | | | S00630 | 5 | C | * | 150-199, 275-299 |
| 136 | 22 | | PA | 13-5 | 25-65-11 | D06404P | 12 | | | | | | D10500 | 5 | | | 150-199, 275-299 |
| 137 | 20 | | PA | 14-7 | 25-65-11 | D06404P | 9 | | | | | | S00630 | 5 | C | * | 150-199, 275-299 |
| 138 | 22 | | PA | 16-10 | 25-65-11 | S00630 | 1 | C | | | | | D10500 | 19 | | | 150-199, 275-299 |
| 139 | 20 | | PA | 1-4 | 25-65-11 | S00630 | 3 | C | | | | | S00632 | 2 | C | * | 150-199, 275-299 |
| 141 | 20 | | PA | 1-0 | 25-65-11 | S00632 | 2 | C | | * | | | S00632 | 5 | C | | 150-199, 275-299 |
| 142 | 20 | | PA | 12-6 | 25-65-11 | D06402P | 6 | | | | | | S00632 | 3 | C | * | 150-199, 275-299 |
| 143 | 20 | | PA | 12-6 | 25-65-11 | D06402P | 8 | | | | | | S00632 | 6 | C | * | 150-199, 275-299 |
| 144 | 18 | | PA | 14-7 | 25-65-11 | D06404P | 24 | DK | | | | | S00632 | 3 | C | * | 150-199, 275-299 |
| 145 | 22 | | PA | 13-5 | 25-65-11 | D06404P | 5 | | | | | | D10500 | 17 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 17

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0786 | 286T0786 | | | R MID EMER LTG (continued) | | | | | | | | | | | | | | |
| 146 | 18 | | PA | | 14-7 | 25-65-11 | D06404P | | 20 | DK | | | | S00632 | 6 | C | * | 150-199, 275-299 |
| 147 | 22 | | PA | | 16-10 | 25-65-11 | S00632 | | 1 | C | | | | D10500 | 6 | | | 150-199, 275-299 |
| 148 | 22 | | PA | | 16-10 | 25-65-11 | S00632 | | 4 | C | | | | D10500 | 7 | | | 150-199, 275-299 |
| 149 | 18 | | PA | | 14-3 | 25-65-12 | D06406P | | 4 | | | | | D06408P | 14 | DK | | 150-199, 275-299 |
| 150 | 20 | | PA | | 12-6 | 25-65-12 | D06406P | | 3 | | | | | S00629 | 2 | C | * | 150-199, 275-299 |
| 151 | 18 | | PA | | 14-3 | 25-65-12 | D06406P | | 7 | | | | | D06408P | 16 | DK | | 150-199, 275-299 |
| 153 | 18 | | PA | | 14-3 | 25-65-12 | D06406P | | 10 | | | | | D06408P | 10 | DK | | 150-199, 275-299 |
| 154 | 20 | | PA | | 1-0 | 25-65-12 | S00629 | | 2 | C | * | | | S00629 | 6 | C | * | 150-199, 275-299 |
| 156 | 22 | | PA | | 12-6 | 25-65-12 | S00629 | | 5 | C | * | | | D06406P | 1 | | | 150-199, 275-299 |
| 157 | 20 | | PA | | 14-0 | 25-65-12 | D06408P | | 9 | | | | | S00629 | 5 | C | * | 150-199, 275-299 |
| 158 | 20 | | PA | | 2-5 | 25-65-12 | S00629 | | 3 | C | | | | S00631 | 2 | C | * | 150-199, 275-299 |
| 159 | 20 | | PA | | 12-6 | 25-65-12 | D06406P | | 6 | | | | | S00631 | 3 | C | * | 150-199, 275-299 |
| 160 | 20 | | PA | | 12-6 | 25-65-12 | D06406P | | 8 | | | | | S00631 | 6 | C | * | 150-199, 275-299 |
| 161 | 18 | | PA | | 14-1 | 25-65-12 | D06408P | | 24 | DK | | | | S00631 | 3 | C | * | 150-199, 275-299 |
| 162 | 18 | | PA | | 14-1 | 25-65-12 | D06408P | | 20 | DK | | | | S00631 | 6 | C | * | 150-199, 275-299 |
| 163 | 22 | | PA | | 16-4 | 25-65-12 | D10502 | | 14 | | | | | D06406P | 2 | | | 150-199, 275-299 |
| 164 | 22 | | PA | | 13-0 | 25-65-12 | D10502 | | 5 | | | | | D06408P | 12 | | | 150-199, 275-299 |
| 165 | 22 | | PA | | 16-2 | 25-65-12 | D10502 | | 19 | | | | | S00629 | 1 | C | | 150-199, 275-299 |
| 166 | 22 | | PA | | 13-0 | 25-65-12 | D10502 | | 17 | | | | | D06408P | 5 | | | 150-199, 275-299 |
| 167 | 22 | | PA | | 16-2 | 25-65-12 | D10502 | | 6 | | | | | S00631 | 1 | C | | 150-199, 275-299 |
| 168 | 22 | | PA | | 16-2 | 25-65-12 | D10502 | | 7 | | | | | S00631 | 4 | C | | 150-199, 275-299 |
| 170 | 20 | | PA | | 1-0 | 25-65-12 | S00631 | | 2 | C | * | | | S00631 | 5 | C | | 150-199, 275-299 |
| 171 | 22 | | PA | | 71-2 | 30-46-11 | D05082P | | 27 | | | | | D05080P | 7 | | | 050-099 |
| 171 | 22 | | PA | | 81-2 | 30-46-11 | D05082P | | 27 | | | | | D05080P | 7 | | | 150-199, 275-299 |
| 175 | 24 | | PK | | 71-2 | 33-21-12 | D05082P | | 30 | | | | | D05080P | 10 | | | 050-099 |
| 175 | 20 | | PA | | 81-2 | 33-21-12 | D05082P | | 30 | | | | | D05080P | 10 | | | 150-199 |
| 176 | 24 | | PK | | 71-2 | 33-21-12 | D05082P | | 31 | | | | | D05080P | 11 | | | 050-099 |
| 176 | 20 | | PA | | 81-2 | 33-21-12 | D05082P | | 31 | | | | | D05080P | 11 | | | 150-199 |
| 201B | 22 | | PB | A | 71-2 | 21-51-22 | D05082P | | 1 | | | | | D05080P | 1 | | | 050-099 |
| 201B | 22 | | PB | A | 81-2 | 21-51-22 | D05082P | | 1 | | | | | D05080P | 1 | | | 150-199, 275-299 |
| 201R | 22 | | PB | A | 0-0 | 21-51-22 | D05082P | | 2 | | | | | D05080P | 2 | | | ALL |
| 202B | 24 | | PL | B | 71-2 | 21-61-31 | D05082P | | 4 | | | | | D05080P | 4 | | | 050-099 |
| 202B | 24 | | PL | B | 81-2 | 21-61-31 | D05082P | | 4 | | | | | D05080P | 4 | | | 150-199, 275-299 |
| 202R | 24 | | PL | B | 0-0 | 21-61-31 | D05082P | | 5 | | | | | D05080P | 5 | | | ALL |
| 203B | 24 | | PL | C | 59-5 | 52-71-12 | D05082P | | 11 | | | | | SP00690 | 9 | | | 050-099 |
| 203B | 24 | | PL | C | 68-10 | 52-71-12 | D05082P | | 11 | | | | | SP00690 | 9 | | | 150-199, 275-299 |
| 203R | 24 | | PL | C | 0-0 | 52-71-12 | D05082P | | 10 | | | | | SP00688 | 9 | | | ALL |
| 204B | 24 | | PL | D | 71-6 | 52-71-12 | D05082P | | 26 | | | | | SP02676 | 9 | | | 150-199, 275-299 |
| 204R | 24 | | PL | D | 0-0 | 52-71-12 | D05082P | | 25 | | | | | SP02674 | 9 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 18

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-----------------------------------|-------------|---------|-------|------|------|--------|-------|---------|-------|--------|------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0786 | 286T0786 | | | R MID EMER LTG (continued) | | | | | | | | | | | | |
| 205B | 24 | PL | IE | 71-2 | 21-61-71 | D05080P | | 9 | | | | D05082P | 29 | | 050-099 | |
| 205B | 24 | PL | IE | 81-2 | 21-61-71 | D05082P | | 29 | | | | D05080P | 9 | | 150-199, 275-299 | |
| 205R | 24 | PL | IE | 0-0 | 21-61-71 | D05080P | | 8 | | | | D05082P | 28 | | 050-099 | |
| 205R | 24 | PL | IE | 0-0 | 21-61-71 | D05082P | | 28 | | | | D05080P | 8 | | 150-199, 275-299 | |
| 814 | 20 | PA | | 71-2 | SPARE | D05082P | | 21 | | | | D05080P | 21 | | 050-099 | |
| 814 | 20 | PA | | 81-2 | SPARE | D05082P | | 21 | | | | D05080P | 21 | | 150-199, 275-299 | |
| A-A | | | | 0-0 | 52-71-12 | SP00688 | | | 9 | | | S00193 | RED | | ALL | |
| A-B | | | | 0-0 | 52-71-12 | SP00690 | | | 9 | | | S00193 | BLU | | ALL | |
| B-A | | | | 0-0 | 33-51-21 | D06326J | | = 1 | | | | L00393 | GND | | ALL | |
| B-B | | | | 0-0 | 33-51-21 | D06324P | | = 1 | | | | L00393 | PWR | | ALL | |
| C-A | | | | 0-0 | 33-51-21 | D06318J | | = 1 | | | | L00392 | GND | | ALL | |
| C-B | | | | 0-0 | 33-51-21 | D06316P | | = 1 | | | | L00392 | PWR | | ALL | |
| D-A | | | | 0-0 | 52-71-12 | S00217 | | | | RED | | SP02674 | | 9 | 150-199, 275-299 | |
| D-B | | | | 0-0 | 52-71-12 | S00217 | | | | BLU | | SP02676 | | 9 | 150-199, 275-299 | |
| W0788 | 286T0788 | | | L AFT EMER LTG | | | | | | | | | | | | |
| 001 | 22 | PA | | 0-7 | 33-51-11 | D01652 | | 5 | | | | D01652 | 6 | | ALL | |
| 002 | 20 | PA | | 38-11 | 33-51-11 | SM00023 | | | | S | | D05084P | 1 | | 050-099 | |
| 002 | 20 | PA | | 49-10 | 33-51-11 | SM00023 | | | | S | | D05084P | 1 | | 150-199 | |
| 002 | 20 | PA | | 51-7 | 33-51-11 | D01652 | | 2 | | | | D05084P | 1 | | 275-299 | |
| 003 | 20 | PA | | 2-2 | 33-51-11 | D01652 | | 1 | | | | GD02598 | D.. E | | 050-099 | |
| 003 | 20 | PA | | 2-9 | 33-51-11 | D01652 | | 1 | | | | GD02598 | D.. E | | 150-199, 275-299 | |
| 004 | 20 | PA | | 2-8 | 33-51-11 | D01652 | | 7 | | | | GD02600 | S.. E | | 050-099 | |
| 004 | 20 | PA | | 3-3 | 33-51-11 | D01652 | | 7 | | | | GD02600 | S.. E | | 150-199, 275-299 | |
| 005 | 22 | PA | | 38-11 | 33-51-11 | SM00024 | | | | S | | D05084P | 2 | | 050-099 | |
| 005 | 22 | PA | | 49-10 | 33-51-11 | SM00024 | | | | S | | D05084P | 2 | | 150-199 | |
| 005 | 22 | PA | | 51-7 | 33-51-11 | D01652 | | 4 | | | | D05084P | 2 | | 275-299 | |
| 006 | 22 | PA | | 36-6 | 33-51-11 | D01652 | | 3 | | | | SM00004 | | S | 050-099 | |
| 006 | 22 | PA | | 47-2 | 33-51-11 | D01652 | | 3 | | | | SM00004 | | S | 150-199, 275-299 | |
| 007 | 22 | PA | | 40-2 | 33-51-11 | D01652 | | 8 | | | | D05084P | 4 | | 050-099 | |
| 007 | 22 | PA | | 51-7 | 33-51-11 | D01652 | | 8 | | | | D05084P | 4 | | 150-199, 275-299 | |
| 008 | 18 | PA | | 35-8 | 33-51-13 | D01652 | | 16 | | DK | | SP00648 | | S | 275-299 | |
| 009 | 20 | PA | | 28-6 | 33-51-13 | D01652 | | 15 | | | | L00334 | 1 C | | 050-099 | |
| 009 | 20 | PA | | 28-9 | 33-51-13 | D01652 | | 15 | | | | L00334 | 1 C | | 150-199, 275-299 | |
| 010 | 18 | PA | | 25-5 | 33-51-13 | L00332 | | 1 | | C | | D01652 | 14 DK | | 050-099 | |
| 010 | 18 | PA | | 34-6 | 33-51-13 | L00422 | | 1 | | C | | D01652 | 14 DK | | 150-199, 275-299 | |
| 011 | 22 | PA | | 22-3 | 33-51-13 | SM00011 | | | | S | | L00332 | 1 C | | 150-199 | |
| 011 | 22 | PA | | 25-0 | 33-51-13 | SM00011 | | | | S | | L00332 | 1 C | | 275-299 | |
| 012 | 18 | PA | | 21-2 | 33-51-13 | D01652 | | 12 | | DK | | L00331 | 1 C | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 19

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------|----|-----------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0788 | 286T0788 | | | L AFT EMER LTG (continued) | | | | | | | | | | | | |
| 012 | 18 | | PA | | 21-6 | 33-51-13 | D01652 | 12 | DK | | L00331 | 1 | C | | 150-199, 275-299 | |
| 013 | 20 | | PA | | 19-4 | 33-51-13 | D01652 | 11 | | | L00330 | 1 | C | | 050-099 | |
| 013 | 20 | | PA | | 1-9 | 33-51-13 | D01652 | 11 | | | SM00011 | | S | | 150-199, 275-299 | |
| 014 | 22 | | PA | | 22-7 | 33-51-13 | D01652 | 10 | | | L00329 | 1 | C | | 050-099 | |
| 014 | 22 | | PA | | 21-2 | 33-51-13 | D01652 | 10 | | | L00329 | 1 | C | | 150-199, 275-299 | |
| 015 | 22 | | PA | | 29-3 | 33-51-13 | D01652 | 9 | | | L00783 | 1 | C | | 150-199, 275-299 | |
| 016 | 20 | | PA | | 6-0 | 33-51-13 | L00783 | 2 | C | | GD04940 | D.. | E | | 150-199, 275-299 | |
| 017 | 20 | | PA | | 5-4 | 33-51-13 | L00329 | 2 | C | | GD02558 | D.. | E | | 050-099 | |
| 017 | 20 | | PA | | 6-1 | 33-51-13 | L00329 | 2 | C | | GD02558 | D.. | E | | 150-199, 275-299 | |
| 018 | 20 | | PA | | 4-11 | 33-51-13 | L00330 | 2 | C | | GD02560 | D.. | E | | 050-099 | |
| 018 | 20 | | PA | | 5-5 | 33-51-13 | L00330 | 2 | C | | GD02560 | D.. | E | | 150-199, 275-299 | |
| 019 | 20 | | PA | | 8-11 | 33-51-13 | L00331 | 2 | C | | GD00026 | D.. | 2 | | 050-099 | |
| 019 | 18 | | PA | | 7-2 | 33-51-13 | L00331 | 2 | C | | GD05078 | D.. | E | | 150-199, 275-299 | |
| 020 | 20 | | PA | | 6-11 | 33-51-13 | L00332 | 2 | C | | GD00026 | D.. | 2 | | 050-099, 150-199 | |
| 020 | 20 | | PA | | 4-4 | 33-51-13 | L00332 | 2 | C | | GD00026 | D.. | 2 | | 275-299 | |
| 022 | 20 | | PA | | 17-11 | 33-51-13 | L00334 | 2 | C | | GD00932 | D.. | 2 | | 050-099 | |
| 022 | 20 | | PA | | 19-0 | 33-51-13 | L00334 | 2 | C | | GD00932 | D.. | 2 | | 150-199, 275-299 | |
| 040 | 22 | | PA | | 0-7 | 33-51-13 | D01652 | 20 | | | D01652 | 24 | | | ALL | |
| 041 | 22 | | PA | | 25-4 | 33-21-21 | L00811 | =P | C | * | L00466 | =P | C | | 150-199, 275-299 | |
| 042 | 20 | | PA | | 5-2 | 33-21-21 | L00811 | =G | C | | GD04938 | A.. | E | | 150-199, 275-299 | |
| 046 | 18 | | PA | | 13-3 | 33-51-13 | L00422 | 2 | C | | GD00932 | D.. | 2 | | 150-199, 275-299 | |
| 048 | 22 | | PA | | 16-7 | 33-51-13 | SM00011 | | S | | L00330 | 1 | C | | 150-199, 275-299 | |
| 050 | 22 | | PA | | 13-11 | 33-21-21 | D05084P | 15 | | | L00464 | =P | C | * | 050-099 | |
| 050 | 22 | | PA | | 18-0 | 33-21-21 | D05084P | 15 | | | L00464 | =P | C | * | 150-199, 275-299 | |
| 051 | 22 | | PA | | 27-5 | 33-21-21 | L00466 | =P | C | | L00464 | =P | C | * | 050-099 | |
| 051 | 22 | | PA | | 26-9 | 33-21-21 | L00811 | =P | C | * | L00464 | =P | C | * | 150-199, 275-299 | |
| 053 | 20 | | PA | | 4-9 | 33-21-21 | L00464 | =G | C | | GD01038 | A.. | E | | 050-099 | |
| 053 | 20 | | PA | | 5-0 | 33-21-21 | L00464 | =G | C | | GD04882 | A.. | E | | 150-199, 275-299 | |
| 054 | 20 | | PA | | 6-2 | 33-21-21 | L00466 | =G | C | | GD01042 | A.. | E | | 050-099 | |
| 054 | 20 | | PA | | 5-5 | 33-21-21 | L00466 | =G | C | | GD01580 | A.. | E | | 150-199, 275-299 | |
| 061 | 22 | | PA | | 4-3 | 33-51-11 | D05084P | 3 | | | SM00004 | | S | | 050-099 | |
| 061 | 22 | | PA | | 4-5 | 33-51-11 | D05084P | 3 | | | SM00004 | | S | | 150-199, 275-299 | |
| 063 | 14 | | PA | | 52-3 | 33-51-21 | SM00008 | | S | | L00389 | 1 | D | | 050-099 | |
| 063 | 14 | | PA | | 65-1 | 33-51-21 | SM00008 | | S | | L00389 | 1 | D | | 150-199 | |
| 063 | 14 | | PA | | 67-2 | 33-51-21 | SM00008 | | S | | L00389 | 1 | D | | 275-299 | |
| 064 | 14 | | PA | | 1-6 | 33-51-21 | L00389 | 2 | D | | GD02584 | D.. | E | | 050-099 | |
| 064 | 14 | | PA | | 2-8 | 33-51-21 | L00389 | 2 | D | | GD04652 | D.. | E | | 150-199, 275-299 | |
| 065 | 20 | | PA | | 55-7 | 33-51-21 | D01080 | 2 | | | D05084P | 7 | | | 050-099 | |
| 065 | 20 | | PA | | 71-8 | 33-51-21 | D01080 | 2 | | | D05084P | 7 | | | 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 20

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|-----------------------------------|-------|----------|---------|------|------|--------|-------|------|------|---------|-------------|---|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0788 | 286T0788 | | | L AFT EMER LTG (continued) | | | | | | | | | | | | | |
| 065 | 20 | PA | | | 73-9 | 33-51-21 | D01080 | | | | 2 | | | D05084P | 7 | | 275-299 |
| 066 | 22 | PA | | | 55-7 | 33-51-21 | D01080 | | | | 4 | | | D05084P | 6 | | 050-099 |
| 066 | 22 | PA | | | 71-8 | 33-51-21 | D01080 | | | | 4 | | | D05084P | 6 | | 150-199 |
| 066 | 22 | PA | | | 73-9 | 33-51-21 | D01080 | | | | 4 | | | D05084P | 6 | | 275-299 |
| 067 | 22 | PA | | | 0-7 | 33-51-21 | D01080 | | | | 24 | | | D01080 | 20 | | ALL |
| 068 | 22 | PA | | | 52-3 | 33-51-21 | D01080 | | | | 3 | | | SM00004 | | S | 050-099 |
| 068 | 22 | PA | | | 68-5 | 33-51-21 | D01080 | | | | 3 | | | SM00004 | | S | 150-199 |
| 068 | 22 | PA | | | 70-6 | 33-51-21 | D01080 | | | | 3 | | | SM00004 | | S | 275-299 |
| 069 | 22 | PA | | | 0-7 | 33-51-21 | D01080 | | | | 6 | | | D01080 | 5 | | ALL |
| 070 | 22 | PA | | | 55-7 | 33-51-21 | D01080 | | | | 8 | | | D05084P | 8 | | 050-099 |
| 070 | 22 | PA | | | 71-8 | 33-51-21 | D01080 | | | | 8 | | | D05084P | 8 | | 150-199 |
| 070 | 22 | PA | | | 73-9 | 33-51-21 | D01080 | | | | 8 | | | D05084P | 8 | | 275-299 |
| 071 | 12 | PA | | | 41-11 | 33-51-21 | SM00009 | | | | | S | | SM00020 | | S | 050-099 |
| 071 | 12 | PA | | | 36-1 | 33-51-21 | SM00009 | | | | | S | | SM00020 | | S | 150-199 |
| 071 | 12 | PA | | | 33-4 | 33-51-21 | SM00009 | | | | | S | | SM00020 | | S | 275-299 |
| 072 | 16 | PA | | | 6-5 | 33-51-21 | GD04734 | | | | D.. | E | | D06330P | = 1 | | 050-099 |
| 072 | 16 | PA | | | 5-5 | 33-51-21 | GD04734 | | | | D.. | E | | D06330P | = 1 | | 150-199, 275-299 |
| 073 | 20 | PA | | | 2-9 | 33-51-21 | D01080 | | | | 7 | | | GD05870 | S.. | E | 050-099 |
| 073 | 20 | PA | | | 1-6 | 33-51-21 | D01080 | | | | 7 | | | GD05670 | S.. | E | 150-199 |
| 073 | 20 | PA | | | 2-11 | 33-51-21 | D01080 | | | | 7 | | | GD02578 | S.. | E | 275-299 |
| 074 | 20 | PA | | | 2-5 | 33-51-21 | D01080 | | | | 1 | | | GD05872 | D.. | E | 050-099 |
| 074 | 20 | PA | | | 1-11 | 33-51-21 | D01080 | | | | 1 | | | GD05668 | D.. | E | 150-199 |
| 074 | 20 | PA | | | 2-7 | 33-51-21 | D01080 | | | | 1 | | | GD02576 | D.. | E | 275-299 |
| 075 | 14 | PA | | | 2-6 | 33-51-21 | L00395 | | | | 2 | D | | GD02716 | D.. | E | ALL |
| 076 | 14 | PA | | | 65-8 | 33-51-21 | L00395 | | | | 1 | D | | SM00006 | | S | 050-099 |
| 076 | 14 | PA | | | 81-8 | 33-51-21 | L00395 | | | | 1 | D | | SM00006 | | S | 150-199 |
| 076 | 14 | PA | | | 83-10 | 33-51-21 | L00395 | | | | 1 | D | | SM00006 | | S | 275-299 |
| 077 | 20 | PA | | | 1-6 | 33-51-21 | D01080 | | | | 11 | | | SM00006 | | S | ALL |
| 078 | 14 | PA | | | 58-1 | 33-51-21 | L00642 | | | | 1 | D | | SM00007 | | S | 050-099 |
| 078 | 14 | PA | | | 73-6 | 33-51-21 | L00642 | | | | 1 | D | | SM00007 | | S | 150-199 |
| 078 | 14 | PA | | | 75-7 | 33-51-21 | L00642 | | | | 1 | D | | SM00007 | | S | 275-299 |
| 079 | 14 | PA | | | 2-6 | 33-51-21 | L00642 | | | | 2 | D | | GD04208 | D.. | E | 050-099 |
| 079 | 14 | PA | | | 3-9 | 33-51-21 | L00642 | | | | 2 | D | | GD04208 | D.. | E | 150-199, 275-299 |
| 080 | 20 | PA | | | 1-6 | 33-51-21 | D01080 | | | | 12 | | | SM00007 | | S | ALL |
| 081 | 20 | PA | | | 1-6 | 33-51-21 | D01080 | | | | 10 | | | SM00008 | | S | ALL |
| 082 | 20 | PA | | | 1-6 | 33-51-21 | D01080 | | | | 9 | | | SM00009 | | S | ALL |
| 090 | 16 | PA | | | 0-6 | 33-51-21 | SM00020 | | | | | S | | D06328J | = 1 | | ALL |
| 108 | 22 | PK | | | 48-4 | 30-46-11 | D05084P | | | | 5 | | | D06612P | 1 | | 050-099 |
| 108 | 22 | PA | | | 60-3 | 30-46-11 | D05084P | | | | 5 | | | D06612P | 1 | | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 21

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0788 | 286T0788 | | | L AFT EMER LTG (continued) | | | | | | | | | | | |
| 108 | 22 | | PK | | 60-3 | 30-46-11 | D05084P | | 5 | | D06612P | | 1 | | 280-299 |
| 109 | 20 | | PK | | 11-0 | 30-46-11 | D06612P | | 2 | | GD01126 | D.. | 2 | | 050-099 |
| 109 | 20 | | PA | | 10-9 | 30-46-11 | D06612P | | 2 | | GD01126 | D.. | 2 | | 150-199, 275-278 |
| 109 | 20 | | PK | | 10-9 | 30-46-11 | D06612P | | 2 | | GD01126 | D.. | 2 | | 280-299 |
| 110 | 20 | | PK | | 11-0 | 30-46-11 | D06612P | | 3 | | GD01126 | S.. | 2 | | 050-099 |
| 110 | 20 | | PA | | 10-9 | 30-46-11 | D06612P | | 3 | | GD01126 | S.. | 2 | | 150-199, 275-278 |
| 110 | 20 | | PK | | 10-9 | 30-46-11 | D06612P | | 3 | | GD01126 | S.. | 2 | | 280-299 |
| 119 | 20 | | PA | | 1-4 | 33-51-17 | D01652 | | 13 | | D11714 | = 1 | | | 275-299 |
| 120 | 20 | | PA | | 2-10 | 33-51-17 | D11716 | | = 1 | | GD02598 | D.. | E | | 275-299 |
| 140 | 22 | | PA | | 47-2 | 33-21-21 | D05084P | | 24 | | L01182 | = P | C | | 050-099 |
| 140 | 22 | | PA | | 58-9 | 33-21-21 | D05084P | | 24 | | L01182 | = P | C | | 162-199 |
| 141 | 20 | | PA | | 19-2 | 33-21-21 | L01182 | | = G | C | GD01580 | A.. | E | | 050-099 |
| 141 | 20 | | PA | | 17-4 | 33-21-21 | L01182 | | = G | C | GD01046 | A.. | E | | 162-199 |
| 201B | 24 | | PL | A | 59-1 | 52-71-11 | D05084P | | 10 | | SP00682 | | 9 | | 050-099 |
| 201B | 24 | | PL | A | 70-1 | 52-71-11 | D05084P | | 10 | | SP00682 | | 9 | | 150-199, 275-299 |
| 201R | 24 | | PL | A | 0-0 | 52-71-11 | D05084P | | 9 | | SP00680 | | 9 | | ALL |
| 202B | 24 | | PL | B | 59-3 | 52-71-11 | D05084P | | 12 | | SP00686 | | 9 | | 050-099 |
| 202B | 24 | | PL | B | 70-4 | 52-71-11 | D05084P | | 12 | | SP00686 | | 9 | | 150-199, 275-299 |
| 202R | 24 | | PL | B | 0-0 | 52-71-11 | D05084P | | 11 | | SP00684 | | 9 | | ALL |
| 203B | 24 | | PL | C | 59-4 | 52-71-11 | D05084P | | 14 | | SP00718 | | 9 | | 050-099 |
| 203B | 24 | | PL | C | 69-4 | 52-71-11 | D05084P | | 14 | | SP00718 | | 9 | | 150-199, 275-299 |
| 203R | 24 | | PL | C | 0-0 | 52-71-11 | D05084P | | 13 | | SP00716 | | 9 | | ALL |
| 600 | 18 | | PA | | 33-2 | 33-51-13 | D01652 | | 9 | DK | L00335 | | 1 | C | 050-099 |
| 601 | 20 | | PA | | 2-0 | 33-51-17 | D13256 | | C | | D13266 | A | | | 150-199 |
| 602 | 20 | | PA | | 2-0 | 33-51-17 | D13256 | | B | | D13266 | B | | | 150-199 |
| 603 | 20 | | PA | | 2-0 | 33-51-17 | D13256 | | F | | D13266 | C | | | 150-199 |
| 604 | 20 | | PA | | 2-0 | 33-51-17 | D13256 | | E | | D13266 | D | | | 150-199 |
| 605 | 20 | | PA | | 2-6 | 33-51-17 | D13256 | | D | | GD05566 | D.. | E | | 150-199 |
| 606 | 22 | | PA | | 41-11 | 33-51-17 | D13256 | | L | | SM00024 | | S | | 150-199 |
| 607 | 22 | | PA | | 25-8 | 33-51-17 | D13256 | | K | | SM00004 | | S | | 150-199 |
| 608 | 20 | | PA | | 41-11 | 33-51-17 | D13256 | | A | | SM00023 | | S | | 150-199 |
| 610 | 20 | | PA | | 2-0 | 33-51-17 | D13262 | | A | | SM00017 | | S | | 050-099, 150-199 |
| 611 | 20 | | PA | | 2-0 | 33-51-17 | D13262 | | B | | SM00018 | | S | | 050-099, 150-199 |
| 612 | 20 | | PA | | 2-0 | 33-51-17 | D13262 | | C | | SM00019 | | S | | 050-099, 150-199 |
| 613 | 20 | | PA | | 2-0 | 33-51-17 | D13262 | | D | | SM00021 | | S | | 050-099, 150-199 |
| 618 | 20 | | PA | | 2-1 | 33-51-14 | D13210 | | C | | SM00017 | | S | | 050-099, 150-199 |
| 619 | 20 | | PA | | 2-1 | 33-51-14 | D13210 | | B | | SM00018 | | S | | 050-099, 150-199 |
| 620 | 20 | | PA | | 2-1 | 33-51-14 | D13210 | | F | | SM00019 | | S | | 050-099, 150-199 |
| 621 | 20 | | PA | | 2-1 | 33-51-14 | D13210 | | E | | SM00021 | | S | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 22

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0788 | 286T0788 | | | L AFT EMER LTG (continued) | | | | | | | | | | | | | |
| 622 | 20 | | PA | 2-6 | 33-51-14 | D13210 | | D | | | | | GD02598 | D.. | E | | 050-099 |
| 622 | 20 | | PA | 3-1 | 33-51-14 | D13210 | | D | | | | | GD02598 | D.. | E | | 150-199 |
| 623 | 22 | | PA | 2-1 | 33-51-14 | D13210 | | L | | | | | SM00024 | | S | | 050-099, 150-199 |
| 624 | 22 | | PA | 36-10 | 33-51-14 | D13210 | | K | | | | | SM00004 | | S | | 050-099 |
| 624 | 22 | | PA | 47-6 | 33-51-14 | D13210 | | K | | | | | SM00004 | | S | | 150-199 |
| 625 | 20 | | PA | 2-1 | 33-51-14 | D13210 | | A | | | | | SM00023 | | S | | 050-099, 150-199 |
| 626 | 20 | | PA | 40-8 | 33-51-14 | D13224 | | A | | | | | SM00017 | | S | | 050-099 |
| 626 | 20 | | PA | 40-10 | 33-51-14 | D13224 | | A | | | | | SM00017 | | S | | 150-199 |
| 627 | 20 | | PA | 40-8 | 33-51-14 | D13224 | | B | | | | | SM00018 | | S | | 050-099 |
| 627 | 20 | | PA | 40-10 | 33-51-14 | D13224 | | B | | | | | SM00018 | | S | | 150-199 |
| 628 | 20 | | PA | 40-8 | 33-51-14 | D13224 | | C | | | | | SM00019 | | S | | 050-099 |
| 628 | 20 | | PA | 40-10 | 33-51-14 | D13224 | | C | | | | | SM00019 | | S | | 150-199 |
| 629 | 20 | | PA | 40-8 | 33-51-14 | D13224 | | D | | | | | SM00021 | | S | | 050-099 |
| 629 | 20 | | PA | 40-10 | 33-51-14 | D13224 | | D | | | | | SM00021 | | S | | 150-199 |
| 630 | 20 | | PA | 44-2 | 33-51-14 | D13226 | | A | | | | | SM00017 | | S | | 150-199 |
| 631 | 20 | | PA | 44-2 | 33-51-14 | D13226 | | B | | | | | SM00018 | | S | | 150-199 |
| 632 | 20 | | PA | 44-2 | 33-51-14 | D13226 | | C | | | | | SM00019 | | S | | 150-199 |
| 633 | 20 | | PA | 44-2 | 33-51-14 | D13226 | | D | | | | | SM00021 | | S | | 150-199 |
| 647 | 20 | | PA | 1-9 | 33-51-11 | SM00023 | | | S | | | | D01652 | | 2 | | 050-099, 150-199 |
| 648 | 20 | | PA | 1-9 | 33-51-11 | SM00024 | | | S | | | | D01652 | | 4 | | 050-099, 150-199 |
| 659 | 20 | | PA | 70-0 | 33-51-17 | D12076 | | B | | | | | SM00018 | | S | | 050-099 |
| 659 | 20 | | PA | 59-8 | 33-51-17 | D12076 | | B | | | | | SM00018 | | S | | 150-199 |
| 660 | 20 | | PA | 70-0 | 33-51-17 | D12076 | | A | | | | | SM00017 | | S | | 050-099 |
| 660 | 20 | | PA | 59-8 | 33-51-17 | D12076 | | A | | | | | SM00017 | | S | | 150-199 |
| 661 | 20 | | PA | 54-8 | 33-51-17 | D12078 | | B | | | | | SM00018 | | S | | 150-199 |
| 662 | 20 | | PA | 54-8 | 33-51-17 | D12078 | | A | | | | | SM00017 | | S | | 150-199 |
| 663 | 20 | | PA | 70-0 | 33-51-17 | D12076 | | D | | | | | SM00021 | | S | | 050-099 |
| 663 | 20 | | PA | 50-5 | 33-51-17 | SM00021 | | | S | | | | SM00030 | | S | | 150-199 |
| 664 | 20 | | PA | 70-0 | 33-51-17 | D12076 | | C | | | | | SM00019 | | S | | 050-099 |
| 664 | 20 | | PA | 50-5 | 33-51-17 | SM00019 | | | S | | | | SM00029 | | S | | 150-199 |
| 665 | 20 | | PA | 4-10 | 33-51-17 | SM00029 | | | S | | | | D12078 | | C | | 150-199 |
| 666 | 20 | | PA | 4-10 | 33-51-17 | SM00030 | | | S | | | | D12078 | | D | | 150-199 |
| 667 | 20 | | PA | 9-10 | 33-51-17 | SM00029 | | | S | | | | D12076 | | C | | 150-199 |
| 668 | 20 | | PA | 9-10 | 33-51-17 | SM00030 | | | S | | | | D12076 | | D | | 150-199 |
| 669 | 18 | | PA | 4-10 | 33-51-13 | L00335 | | 2 | C | | | | GD00932 | | D.. | 2 | 050-099 |
| A-A | | | | 0-0 | 52-71-11 | SP00680 | | | 9 | | | | S00204 | | RED | | ALL |
| A-B | | | | 0-0 | 52-71-11 | SP00682 | | | 9 | | | | S00204 | | BLU | | ALL |
| B-A | | | | 0-0 | 52-71-11 | SP00684 | | | 9 | | | | S00205 | | RED | | ALL |
| B-B | | | | 0-0 | 52-71-11 | SP00686 | | | 9 | | | | S00205 | | BLU | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0780

Page 23

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|-----------------------------------|---------|------|------|--------|-------|------|------|--------|-------------|--------|-----|--|-----|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0788 | 286T0788 | L AFT EMER LTG (continued) | | | | | | | | | | | | | |
| C-A | | 0-0 52-71-11 | SP00716 | | | | | | | | 9 | S00212 | RED | | ALL |
| C-B | | 0-0 52-71-11 | SP00718 | | | | | | | | 9 | S00212 | BLU | | ALL |
| D-A | | 0-0 33-51-21 | D06330J | | | | = 1 | | | | | L00388 | GND | | ALL |
| D-B | | 0-0 33-51-21 | D06328P | | | | = 1 | | | | | L00388 | PWR | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0780
Page 24 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | | |
|------------------------|-----------------|----|----|-----------------------|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|---------|-----|----|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | |
| W0790 | 286T0790 | | | R AFT EMER LTG | | | | | | | | | | | | | | | | |
| 001 | 20 | | PA | 1-0 | 21-65-11 | SM00001 | | | | | | | | 9 | | D03996 | B | | | ALL |
| 002 | 20 | | PA | 10-7 | 21-65-11 | SM00001 | | | | | | | | 9 | | GD04674 | D.. | 2 | | 050-099 |
| 002 | 20 | | PA | 10-1 | 21-65-11 | SM00001 | | | | | | | | 9 | | GD04674 | D.. | 2 | | 150-199 |
| 002 | 20 | | PA | 9-0 | 21-65-11 | SM00001 | | | | | | | | 9 | | GD04674 | D.. | 2 | | 275-299 |
| 003 | 22 | | PA | 0-7 | 33-51-11 | D00170 | | | | | | | 5 | | | D00170 | | 6 | | ALL |
| 004 | 20 | | PA | 46-2 | 33-51-11 | SM00045 | | | | | | | | S | | D05086P | | 7 | | 050-099 |
| 004 | 20 | | PA | 58-11 | 33-51-11 | SM00045 | | | | | | | | S | | D05086P | | 7 | | 150-199 |
| 004 | 20 | | PA | 58-11 | 33-51-11 | D00170 | | | | | | | 2 | | | D05086P | | 7 | | 275-299 |
| 005 | 20 | | PA | 2-3 | 33-51-11 | D00170 | | | | | | | 1 | | | GD04618 | D.. | E | | 050-099 |
| 005 | 20 | | PA | 2-5 | 33-51-11 | D00170 | | | | | | | 1 | | | GD04618 | D.. | E | | 150-199, 275-299 |
| 006 | 20 | | PA | 2-11 | 33-51-11 | D00170 | | | | | | | 7 | | | GD04620 | S.. | E | | 050-099 |
| 006 | 20 | | PA | 2-5 | 33-51-11 | D00170 | | | | | | | 7 | | | GD04620 | S.. | E | | 150-199, 275-299 |
| 007 | 22 | | PA | 46-2 | 33-51-11 | SM00043 | | | | | | | | S | | D05086P | | 8 | | 050-099 |
| 007 | 22 | | PA | 58-11 | 33-51-11 | SM00043 | | | | | | | | S | | D05086P | | 8 | | 150-199 |
| 007 | 22 | | PA | 58-11 | 33-51-11 | D00170 | | | | | | | 4 | | | D05086P | | 8 | | 275-299 |
| 008 | 22 | | PA | 45-5 | 33-51-11 | SM00044 | | | | | | | | S | | SM00005 | | | S | 050-099 |
| 008 | 22 | | PA | 57-5 | 33-51-11 | SM00044 | | | | | | | | S | | SM00005 | | | S | 150-199 |
| 008 | 22 | | PA | 57-5 | 33-51-11 | D00170 | | | | | | | 3 | | | SM00005 | | | S | 275-299 |
| 009 | 22 | | PA | 47-10 | 33-51-11 | D00170 | | | | | | | 8 | | | D05086P | | 10 | | 050-099 |
| 009 | 22 | | PA | 58-11 | 33-51-11 | D00170 | | | | | | | 8 | | | D05086P | | 10 | | 150-199, 275-299 |
| 011 | 16 | | PA | 27-7 | 33-51-12 | D00170 | | | | | | | 15 | FM | | L00311 | | 1 | C | 150-199 |
| 011 | 16 | | PA | 36-8 | 33-51-12 | D00170 | | | | | | | 15 | FM | | SP00650 | | | S | 275-299 |
| 012 | 22 | | PA | 27-11 | 33-51-12 | D00170 | | | | | | | 14 | | | L00309 | | 1 | C | 050-099 |
| 012 | 22 | | PA | 28-2 | 33-51-12 | D00170 | | | | | | | 14 | | | L00309 | | 1 | C | 150-199, 275-299 |
| 013 | 16 | | PA | 32-4 | 33-51-12 | D00170 | | | | | | | 13 | FM | | L00311 | | 1 | C | 050-099 |
| 013 | 18 | | PA | 31-2 | 33-51-12 | D00170 | | | | | | | 13 | DK | | L00779 | | 1 | C | 150-199, 275-299 |
| 014 | 18 | | PA | 22-11 | 33-51-12 | D00170 | | | | | | | 12 | DK | | L00307 | | 1 | C | 050-099 |
| 014 | 18 | | PA | 0-7 | 33-51-12 | D00170 | | | | | | | 12 | DK | | SM00003 | | | S | 150-199 |
| 014 | 18 | | PA | 2-4 | 33-51-12 | D00170 | | | | | | | 12 | DK | | SM00003 | | | S | 275-299 |
| 015 | 18 | | PA | 19-10 | 33-51-12 | D00170 | | | | | | | 11 | DK | | L00306 | | 1 | C | ALL |
| 016 | 22 | | PA | 15-5 | 33-51-12 | D00170 | | | | | | | 10 | | | L00305 | | 1 | C | 050-099 |
| 016 | 22 | | PA | 13-10 | 33-51-12 | D00170 | | | | | | | 10 | | | L00305 | | 1 | C | 150-199, 275-299 |
| 017 | 20 | | PA | 26-0 | 33-51-12 | D00170 | | | | | | | 9 | | | L00304 | | 1 | C | 050-099 |
| 017 | 20 | | PA | 23-11 | 33-51-12 | D00170 | | | | | | | 9 | | | L00304 | | 1 | C | 150-199, 275-299 |
| 018 | 20 | | PA | 6-8 | 33-51-12 | L00304 | | | | | | | 2 | C | | GD02510 | D.. | E | | 050-099 |
| 018 | 20 | | PA | 6-0 | 33-51-12 | L00304 | | | | | | | 2 | C | | GD02510 | D.. | E | | 150-199, 275-299 |
| 019 | 20 | | PA | 6-8 | 33-51-12 | L00305 | | | | | | | 2 | C | | GD02512 | D.. | E | | 050-099 |
| 019 | 20 | | PA | 5-4 | 33-51-12 | L00305 | | | | | | | 2 | C | | GD02512 | D.. | E | | 150-199, 275-299 |
| 020 | 20 | | PA | 8-7 | 33-51-12 | L00306 | | | | | | | 2 | C | | GD00020 | D.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0790

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0790 | 286T0790 | | | R AFT EMER LTG (continued) | | | | | | | | | | | | | |
| 020 | 18 | | PA | 8-11 | 33-51-12 | L00306 | | 2 | C | | | | GD00020 | D.. | 2 | | 150-199, 275-278 |
| 020 | 18 | | PA | 8-9 | 33-51-12 | L00306 | | 2 | C | | | | GD00020 | D.. | 2 | | 280-299 |
| 021 | 20 | | PA | 7-1 | 33-51-12 | L00307 | | 2 | C | | | | GD00020 | D.. | 2 | | 050-099 |
| 021 | 20 | | PA | 7-3 | 33-51-12 | L00307 | | 2 | C | | | | GD00020 | D.. | 2 | | 150-199 |
| 021 | 20 | | PA | 6-6 | 33-51-12 | L00307 | | 2 | C | | | | GD00020 | D.. | 2 | | 275-299 |
| 023 | 20 | | PA | 4-6 | 33-51-12 | L00309 | | 2 | C | | | | GD00020 | D.. | 2 | | 050-099 |
| 023 | 20 | | PA | 5-0 | 33-51-12 | L00309 | | 2 | C | | | | GD00020 | D.. | 2 | | 150-199, 275-299 |
| 024 | 20 | | PA | 14-10 | 33-51-12 | L00310 | | 2 | C | | | | GD00020 | D.. | 2 | | 150-199 |
| 024 | 20 | | PA | 10-9 | 33-51-12 | L00310 | | 2 | C | | | | GD00070 | D.. | 2 | | 275-299 |
| 027 | 20 | | PA | 32-4 | 33-51-12 | SM00003 | | | S | | | | L00310 | | 1 | C | 150-199 |
| 027 | 20 | | PA | 30-6 | 33-51-12 | L00310 | | 1 | C | | | | SM00003 | | | S | 275-299 |
| 028 | 20 | | PA | 3-0 | 33-51-11 | D01088 | | 7 | | | | | GD02586 | S.. | | E | 050-099 |
| 028 | 20 | | PA | 3-4 | 33-51-11 | D01088 | | 7 | | | | | GD05678 | S.. | | E | 150-199 |
| 028 | 20 | | PA | 3-8 | 33-51-11 | D01088 | | 7 | | | | | GD04634 | S.. | | E | 275-299 |
| 029 | 20 | | PA | 3-0 | 33-51-11 | D01088 | | 1 | | | | | GD02584 | D.. | | E | 050-099 |
| 029 | 20 | | PA | 3-4 | 33-51-11 | D01088 | | 1 | | | | | GD05676 | D.. | | E | 150-199 |
| 029 | 20 | | PA | 3-8 | 33-51-11 | D01088 | | 1 | | | | | GD04208 | D.. | | E | 275-299 |
| 030 | 22 | | PA | 25-2 | 33-51-11 | D01088 | | 8 | | | | | D05086P | | 11 | | 050-099 |
| 030 | 22 | | PA | 17-5 | 33-51-11 | D01088 | | 8 | | | | | D05086P | | 11 | | 150-199 |
| 030 | 22 | | PA | 20-8 | 33-51-11 | D01088 | | 8 | | | | | D05086P | | 11 | | 275-299 |
| 031 | 20 | | PA | 24-4 | 33-51-11 | SM00042 | | | S | | | | D05086P | | 12 | | 050-099 |
| 031 | 20 | | PA | 17-5 | 33-51-11 | SM00042 | | | S | | | | D05086P | | 12 | | 150-199 |
| 031 | 20 | | PA | 20-8 | 33-51-11 | D01088 | | 2 | | | | | D05086P | | 12 | | 275-299 |
| 032 | 22 | | PA | 23-2 | 33-51-11 | D01088 | | 3 | | | | | SM00005 | | | S | 050-099 |
| 032 | 22 | | PA | 16-10 | 33-51-11 | D01088 | | 3 | | | | | SM00005 | | | S | 150-199 |
| 032 | 22 | | PA | 20-1 | 33-51-11 | D01088 | | 3 | | | | | SM00005 | | | S | 275-299 |
| 033 | 22 | | PA | 24-4 | 33-51-11 | SM00041 | | | S | | | | D05086P | | 14 | | 050-099 |
| 033 | 22 | | PA | 17-5 | 33-51-11 | SM00041 | | | S | | | | D05086P | | 14 | | 150-199 |
| 033 | 22 | | PA | 20-8 | 33-51-11 | D01088 | | 4 | | | | | D05086P | | 14 | | 275-299 |
| 034 | 22 | | PA | 0-7 | 33-51-11 | D01088 | | 6 | | | | | D01088 | | 5 | | ALL |
| 036 | 18 | | PA | 43-0 | 33-51-13 | L00328 | | 1 | C | | | | D01088 | 10 | | DK | 050-099 |
| 036 | 18 | | PA | 35-1 | 33-51-13 | L00782 | | 1 | C | | | | D01088 | 10 | | DK | 150-199 |
| 036 | 18 | | PA | 38-4 | 33-51-13 | L00782 | | 1 | C | | | | D01088 | 10 | | DK | 275-299 |
| 037 | 18 | | PA | 27-10 | 33-51-13 | D01088 | | 11 | DK | | | | L00326 | | 1 | C | 050-099 |
| 037 | 18 | | PA | 0-3 | 33-51-13 | D01088 | | 11 | DK | | | | SM00011 | | | S | 150-199 |
| 037 | 18 | | PA | 17-10 | 33-51-13 | D01088 | | 11 | DK | | | | SM00011 | | | S | 275-299 |
| 038 | 16 | | PA | 4-6 | 33-51-12 | GD00070 | | D.. | 2 | | | | L00311 | | 2 | C | 050-099 |
| 038 | 16 | | PA | 10-1 | 33-51-12 | L00311 | | 2 | C | | | | GD00020 | D.. | 2 | | 150-199 |
| 042 | 18 | | PA | 44-10 | 33-51-13 | D01088 | | 16 | DK | | | | L00781 | | 1 | C | 150-199 |

WIRE LIST

D280T132

91-21-11
Section W0790
Page 2
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0790 | 286T0790 | | | R AFT EMER LTG (continued) | | | | | | | | | | | | | |
| 042 | 18 | | PA | 42-8 | 33-51-13 | D01088 | | 16 | DK | | | | L00781 | 1 | C | | 275-278 |
| 042 | 18 | | PA | 41-10 | 33-51-13 | D01088 | | 16 | DK | | | | L00781 | 1 | C | | 280-299 |
| 043 | 20 | | PA | 21-1 | 33-51-13 | D01088 | | 15 | | | | | L00325 | 1 | C | | 050-099 |
| 043 | 20 | | PA | 23-6 | 33-51-13 | D01088 | | 15 | | | | | L00326 | 1 | C | | 150-199 |
| 043 | 20 | | PA | 13-7 | 33-51-13 | D01088 | | 15 | | | | | L00326 | 1 | C | | 275-299 |
| 044 | 16 | | PA | 29-1 | 33-51-13 | D01088 | | 14 | FM | | | | L01049 | 1 | C | | 050-099 |
| 047 | 22 | | PA | 0-7 | 33-51-13 | D01088 | | 20 | | | | | D01088 | 24 | | | ALL |
| 048 | 18 | | PA | 24-8 | 33-51-13 | L00323 | | 1 | C | | | | D01088 | 12 | DK | | 050-099 |
| 048 | 18 | | PA | 23-6 | 33-51-13 | L00323 | | 1 | C | | | | D01088 | 12 | DK | | 150-154, 156, 162-199 |
| 048 | 18 | | PA | 24-4 | 33-51-13 | ST0932L | REF | * | | * | | | D01088 | 12 | DK | | 155, 157 |
| 048 | 18 | | PA | 28-5 | 33-51-13 | L00323 | | 1 | C | | | | D01088 | 12 | DK | | 275-276 |
| 048 | 18 | | PA | 27-7 | 33-51-13 | L00323 | | 1 | C | | | | D01088 | 12 | DK | | 277-299 |
| 049 | 20 | | PA | 20-1 | 33-51-13 | L00327 | | 1 | C | | | | SM00011 | | S | | 150-199 |
| 049 | 20 | | PA | 6-6 | 33-51-13 | L00327 | | 1 | C | | | | SM00011 | | S | | 275-299 |
| 050 | 18 | | PA | 8-5 | 33-51-13 | L00327 | | 2 | C | | | | GD02554 | D.. | E | | 050-099 |
| 050 | 20 | | PA | 10-4 | 33-51-13 | L00327 | | 2 | C | | | | GD04912 | D.. | E | | 150-199, 275-299 |
| 051 | 20 | | PA | 9-11 | 33-51-13 | L00326 | | 2 | C | | | | GD02552 | D.. | E | | 050-099 |
| 051 | 20 | | PA | 14-11 | 33-51-13 | L00326 | | 2 | C | | | | GD04656 | D.. | E | | 150-199 |
| 051 | 20 | | PA | 5-1 | 33-51-13 | L00326 | | 2 | C | | | | GD04990 | D.. | E | | 275-299 |
| 052 | 20 | | PA | 10-11 | 33-51-13 | L00325 | | 2 | C | | | | GD04446 | D.. | E | | 050-099 |
| 052 | 20 | | PA | 12-5 | 33-51-13 | L00325 | | 2 | C | | | | GD01944 | D.. | 2 | | 150-199 |
| 053 | 18 | | PA | 10-8 | 33-51-13 | L00323 | | 2 | C | | | | GD02548 | D.. | E | | 050-099 |
| 053 | 18 | | PA | 12-6 | 33-51-13 | L00323 | | 2 | C | | | | GD04656 | D.. | E | | 150-154, 156, 162-199 |
| 053 | 18 | | PA | 15-9 | 33-51-13 | ST0932L | REF | * | | | | | GD04656 | D.. | E | | 155, 157 |
| 053 | 18 | | PA | 8-7 | 33-51-13 | L00323 | | 2 | C | | | | GD04656 | D.. | E | | 275-276 |
| 053 | 18 | | PA | 15-2 | 33-51-13 | L00323 | | 2 | C | | | | GD00683 | D.. | E | | 277-299 |
| 055 | 20 | | PA | 9-10 | 33-51-13 | L00320 | | 2 | C | | | | GD02542 | D.. | E | | 050-099 |
| 055 | 20 | | PA | 11-1 | 33-51-13 | L00320 | | 2 | C | | | | GD02542 | D.. | E | | 150-199 |
| 055 | 20 | | PA | 6-6 | 33-51-13 | L00320 | | 2 | C | | * | | GD02542 | D.. | E | | 275-299 |
| 056 | 20 | | PA | 28-4 | 33-51-13 | L00320 | | 1 | C | | | | D01088 | 9 | | | 050-099 |
| 056 | 18 | | PA | 0-3 | 33-51-13 | SM00014 | | | S | | | | D01088 | 9 | DK | | 150-199 |
| 056 | 18 | | PA | 32-8 | 33-51-13 | L00320 | | 1 | C | | * | | D01088 | 9 | DK | | 275-299 |
| 057 | 22 | | PA | 2-7 | 33-51-11 | D05086P | | 9 | | | | | SM00005 | | S | | 050-099 |
| 057 | 22 | | PA | 2-1 | 33-51-11 | D05086P | | 9 | | | | | SM00005 | | S | | 150-199, 275-299 |
| 058 | 22 | | PA | 0-7 | 33-51-12 | D00170 | | 20 | | | | | D00170 | 24 | | | ALL |
| 059 | 18 | | PA | 4-11 | 33-51-12 | GD04896 | | D.. | E | | | | L00779 | 2 | C | | 150-199, 275-299 |
| 061 | 18 | | PA | 27-6 | 33-51-13 | L00328 | | 1 | C | | | | SM00011 | | S | | 150-199 |
| 061 | 18 | | PA | 13-11 | 33-51-13 | L00328 | | 1 | C | | | | SM00011 | | S | | 275-299 |
| 062 | 18 | | PA | 10-0 | 33-51-13 | L00328 | | 2 | C | | | | GD02556 | D.. | E | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0790

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|-----------------------------------|-------|----------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0790 | 286T0790 | | | R AFT EMER LTG (continued) | | | | | | | | | | | | | | |
| 062 | 18 | PA | | | 5-3 | 33-51-13 | L00328 | | 2 | C | | | | GD04884 | D.. | E | | 150-199, 275-299 |
| 064 | 18 | PA | | | 10-3 | 33-51-13 | L00781 | | 2 | C | | | | GD04992 | D.. | E | | 150-199 |
| 064 | 18 | PA | | | 6-4 | 33-51-13 | L00781 | | 2 | C | | | | GD04992 | D.. | E | | 275-278 |
| 064 | 18 | PA | | | 13-2 | 33-51-13 | L00781 | | 2 | C | | | | GD04992 | D.. | E | | 280-299 |
| 068 | 18 | PA | | | 5-3 | 33-51-13 | L00782 | | 2 | C | | | | GD04924 | D.. | E | | 150-199, 275-299 |
| 070 | 22 | PA | | | 38-7 | 33-51-12 | L00778 | | 1 | C | | | | D00170 | 16 | | | 150-199, 275-299 |
| 071 | 20 | PA | | | 5-0 | 33-51-12 | L00778 | | 2 | C | | | | GD04946 | D.. | E | | 150-199, 275-299 |
| 076 | 20 | PA | | | 27-7 | 33-51-13 | D06652J | | 1 | | | | | SM00014 | | S | | 150-199 |
| 077 | 20 | PA | | | 19-9 | 33-51-13 | D06652J | | 2 | | | | | GD01944 | D.. | 2 | | 150-199 |
| 087 | 20 | PA | | | 37-11 | 33-51-13 | L00320 | | 1 | C | | | | SM00014 | | S | | 150-199 |
| 116 | 20 | PA | | | 21-9 | 33-51-12 | L00307 | | 1 | C | | | | SM00003 | | S | | 150-199 |
| 116 | 20 | PA | | | 22-6 | 33-51-12 | L00307 | | 1 | C | | | | SM00003 | | S | | 275-299 |
| 119 | 18 | PA | | | 34-9 | 33-51-13 | D01088 | | 13 | DK | | | | L00327 | 1 | C | | 050-099 |
| 119 | 18 | PA | | | 29-2 | 33-51-13 | D01088 | | 13 | DK | | | | L00325 | 1 | C | | 150-199 |
| 119 | 20 | PA | | | 1-6 | 33-51-17 | D01088 | | 13 | | | | | D11710 | =1 | | | 275-299 |
| 120 | 20 | PA | | | 3-11 | 33-51-17 | D11712 | | =1 | | | | | GD04208 | D.. | E | | 275-299 |
| 125 | 22 | PK | | | 53-11 | 30-46-11 | D05086P | | 13 | | | | | D06614P | 1 | | | 050-099 |
| 125 | 22 | PK | | | 64-10 | 30-46-11 | D05086P | | 13 | | | | | D06614P | 1 | | | 150-199, 275-299 |
| 126 | 20 | PK | | | 10-6 | 30-46-11 | D06614P | | 2 | | | | | GD01120 | D.. | 2 | | ALL |
| 127 | 20 | PK | | | 10-6 | 30-46-11 | D06614P | | 3 | | | | | GD01120 | S.. | 2 | | ALL |
| 128 | 16 | PA | | | 10-7 | 33-51-13 | L01049 | | 2 | C | | | | GD02542 | D.. | E | | 050-099 |
| 130 | 20 | PA | | | 3-0 | 33-51-13 | L00320 | | 2 | C | * | | | L01049 | 2 | C | | 275-299 |
| 164 | 16 | PA | | | 20-0 | 33-51-13 | L00323 | | 1 | C | | | | ST0932L | REF | * | * | 155, 157 |
| 165 | 16 | PA | | | 14-8 | 33-51-13 | L00323 | | 2 | C | | | | GD01944 | D.. | 2 | | 155, 157 |
| 171 | 20 | PA | | | 3-0 | 33-51-13 | L00320 | | 1 | C | * | | | L01049 | 1 | C | | 275-299 |
| 184 | 18 | PA | | | 32-7 | 33-51-13 | L00655 | | 1 | C | | | | SM00014 | | S | | 155, 157 |
| 190 | 18 | PA | | | 6-5 | 33-51-13 | L00655 | | 2 | C | | | | GD01944 | D.. | 2 | | 155, 157 |
| 201B | 22 | PB | A | | 48-1 | 21-51-22 | D05086P | | 1 | | | | | D02828 | 4 | | | 050-099 |
| 201B | 22 | PB | A | | 60-0 | 21-51-22 | D05086P | | 1 | | | | | D02828 | 4 | | | 150-199, 275-299 |
| 201R | 22 | PB | A | | 0-0 | 21-51-22 | D05086P | | 2 | | | | | D02828 | 3 | | | ALL |
| 202B | 24 | PL | B | | 48-1 | 21-61-31 | D05086P | | 3 | | | | | D02828 | 1 | | | 050-099 |
| 202B | 24 | PL | B | | 60-0 | 21-61-31 | D05086P | | 3 | | | | | D02828 | 1 | | | 150-199, 275-299 |
| 202R | 24 | PL | B | | 0-0 | 21-61-31 | D05086P | | 4 | | | | | D02828 | 2 | | | ALL |
| 203B | 20 | PB | C | | 48-2 | 21-65-11 | D05086P | | 5 | | | | | D03996 | A | | | 050-099 |
| 203B | 20 | PB | IC | | 59-11 | 21-65-11 | D05086P | | 5 | | | | | D03996 | A | | | 150-199 |
| 203B | 20 | PB | C | | 57-11 | 21-65-11 | D05086P | | 5 | | | | | D03996 | A | | | 275-299 |
| 203R | 20 | PB | C | | 0-0 | 21-65-11 | D05086P | | 6 | | | | | SM00001 | | 9 | | 050-099, 275-299 |
| 203R | 20 | PB | IC | | 0-0 | 21-65-11 | D05086P | | 6 | | | | | SM00001 | | 9 | | 150-199 |
| 204B | 24 | PL | D | | 62-10 | 52-71-11 | D05086P | | 16 | | | | | SP00674 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0790

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0790 | 286T0790 | | | R AFT EMER LTG (continued) | | | | | | | | | | | |
| 204B | 24 | PL | D | 73-11 | 52-71-11 | D05086P | | 16 | | | SP00674 | | 9 | | 150-199, 275-299 |
| 204R | 24 | PL | D | 0-0 | 52-71-11 | D05086P | | 15 | | | SP00672 | | 9 | | ALL |
| 205B | 24 | PL | E | 62-10 | 52-71-11 | D05086P | | 18 | | | SP00678 | | 9 | | 050-099 |
| 205B | 24 | PL | E | 73-11 | 52-71-11 | D05086P | | 18 | | | SP00678 | | 9 | | 150-199, 275-299 |
| 205R | 24 | PL | E | 0-0 | 52-71-11 | D05086P | | 17 | | | SP00676 | | 9 | | ALL |
| 206B | 24 | PL | F | 62-11 | 52-71-11 | D05086P | | 20 | | | SP01974 | | 9 | | 050-099 |
| 206B | 24 | PL | F | 73-8 | 52-71-11 | D05086P | | 20 | | | SP01974 | | 9 | | 150-199, 275-299 |
| 206R | 24 | PL | F | 0-0 | 52-71-11 | D05086P | | 19 | | | SP01972 | | 9 | | ALL |
| 215B | 24 | PL | IO | 40-10 | 21-61-71 | D05086P | | 21 | | | D13464 | 1 | | | 050-099 |
| 215B | 24 | PL | IO | 40-6 | 21-61-71 | D05086P | | 29 | | | D13464 | 1 | | | 150-199 |
| 215B | 24 | PL | IO | 40-5 | 21-61-71 | D05086P | | 21 | | | D13464 | 1 | | | 275-299 |
| 215R | 24 | PL | IO | 0-0 | 21-61-71 | D05086P | | 22 | | | D13464 | 2 | | | 050-099, 275-299 |
| 215R | 24 | PL | IO | 0-0 | 21-61-71 | D05086P | | 30 | | | D13464 | 2 | | | 150-199 |
| 601 | 20 | PA | | 2-4 | 33-51-14 | D13208 | | C | | | SM00032 | | S | | 050-099 |
| 601 | 20 | PA | | 1-8 | 33-51-14 | D13208 | | C | | | SM00032 | | S | | 150-199 |
| 602 | 20 | PA | | 2-4 | 33-51-14 | D13208 | | B | | | SM00033 | | S | | 050-099 |
| 602 | 20 | PA | | 1-8 | 33-51-14 | D13208 | | B | | | SM00033 | | S | | 150-199 |
| 603 | 20 | PA | | 2-4 | 33-51-14 | D13208 | | F | | | SM00034 | | S | | 050-099 |
| 603 | 20 | PA | | 1-8 | 33-51-14 | D13208 | | F | | | SM00034 | | S | | 150-199 |
| 604 | 20 | PA | | 2-4 | 33-51-14 | D13208 | | E | | | SM00035 | | S | | 050-099 |
| 604 | 20 | PA | | 1-8 | 33-51-14 | D13208 | | E | | | SM00035 | | S | | 150-199 |
| 605 | 20 | PA | | 4-0 | 33-51-14 | D13208 | | D | | | GD02584 | D.. | E | | 050-099 |
| 605 | 20 | PA | | 4-0 | 33-51-14 | D13208 | | D | | | GD05676 | D.. | E | | 150-199 |
| 606 | 22 | PA | | 2-4 | 33-51-14 | D13208 | | L | | | SM00041 | | S | | 050-099 |
| 606 | 22 | PA | | 2-5 | 33-51-14 | D13208 | | L | | | SM00041 | | S | | 150-199 |
| 607 | 22 | PA | | 24-2 | 33-51-14 | D13208 | | K | | | SM00005 | | S | | 050-099 |
| 607 | 22 | PA | | 17-6 | 33-51-14 | D13208 | | K | | | SM00005 | | S | | 150-199 |
| 608 | 20 | PA | | 2-4 | 33-51-14 | D13208 | | A | | | SM00042 | | S | | 050-099 |
| 608 | 20 | PA | | 2-5 | 33-51-14 | D13208 | | A | | | SM00042 | | S | | 150-199 |
| 610 | 20 | PA | | 35-11 | 33-51-14 | D13212 | | A | | | SM00032 | | S | | 150-199 |
| 611 | 20 | PA | | 35-11 | 33-51-14 | D13212 | | B | | | SM00033 | | S | | 150-199 |
| 612 | 20 | PA | | 35-11 | 33-51-14 | D13212 | | C | | | SM00034 | | S | | 150-199 |
| 613 | 20 | PA | | 35-11 | 33-51-14 | D13212 | | D | | | SM00035 | | S | | 150-199 |
| 614 | 20 | PA | | 28-3 | 33-51-14 | D13220 | | A | | | SM00032 | | S | | 050-099 |
| 614 | 20 | PA | | 38-3 | 33-51-14 | D13220 | | A | | | SM00032 | | S | | 150-199 |
| 615 | 20 | PA | | 28-3 | 33-51-14 | D13220 | | B | | | SM00033 | | S | | 050-099 |
| 615 | 20 | PA | | 38-3 | 33-51-14 | D13220 | | B | | | SM00033 | | S | | 150-199 |
| 616 | 20 | PA | | 28-3 | 33-51-14 | D13220 | | C | | | SM00034 | | S | | 050-099 |
| 616 | 20 | PA | | 38-3 | 33-51-14 | D13220 | | C | | | SM00034 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0790

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0790 | 286T0790 | | | R AFT EMER LTG (continued) | | | | | | | | | | | |
| 617 | 20 | | PA | | 28-3 | 33-51-14 | D13220 | | D | | SM00035 | | S | | 050-099 |
| 617 | 20 | | PA | | 38-3 | 33-51-14 | D13220 | | D | | SM00035 | | S | | 150-199 |
| 618 | 20 | | PA | | 8-5 | 33-51-14 | D13214 | | A | | SM00036 | | S | | 150-199 |
| 619 | 20 | | PA | | 8-5 | 33-51-14 | D13214 | | B | | SM00037 | | S | | 150-199 |
| 620 | 20 | | PA | | 8-5 | 33-51-14 | D13214 | | C | | SM00038 | | S | | 150-199 |
| 621 | 20 | | PA | | 8-5 | 33-51-14 | D13214 | | D | | SM00039 | | S | | 150-199 |
| 622 | 20 | | PA | | 10-9 | 33-51-14 | D13222 | | A | | SM00036 | | S | | 150-199 |
| 623 | 20 | | PA | | 10-9 | 33-51-14 | D13222 | | B | | SM00037 | | S | | 150-199 |
| 624 | 20 | | PA | | 10-9 | 33-51-14 | D13222 | | C | | SM00038 | | S | | 150-199 |
| 625 | 20 | | PA | | 10-9 | 33-51-14 | D13222 | | D | | SM00039 | | S | | 150-199 |
| 626 | 20 | | PA | | 37-3 | 33-51-14 | SM00032 | | | S | SM00036 | | S | | 150-199 |
| 627 | 20 | | PA | | 37-3 | 33-51-14 | SM00033 | | | S | SM00037 | | S | | 150-199 |
| 628 | 20 | | PA | | 37-3 | 33-51-14 | SM00034 | | | S | SM00038 | | S | | 150-199 |
| 629 | 20 | | PA | | 37-3 | 33-51-14 | SM00035 | | | S | SM00039 | | S | | 150-199 |
| 630 | 20 | | PA | | 14-1 | 33-51-16 | D13244 | | C | | SM00047 | | S | | 050-099 |
| 630 | 20 | | PA | | 2-11 | 33-51-16 | D13244 | | C | | SM00047 | | S | | 150-199 |
| 631 | 20 | | PA | | 14-1 | 33-51-16 | D13244 | | B | | SM00046 | | S | | 050-099 |
| 631 | 20 | | PA | | 2-11 | 33-51-16 | D13244 | | B | | SM00046 | | S | | 150-199 |
| 632 | 20 | | PA | | 14-1 | 33-51-16 | D13244 | | F | | SM00052 | | S | | 050-099 |
| 632 | 20 | | PA | | 2-11 | 33-51-16 | D13244 | | F | | SM00052 | | S | | 150-199 |
| 633 | 20 | | PA | | 14-1 | 33-51-16 | D13244 | | E | | SM00051 | | S | | 050-099 |
| 633 | 20 | | PA | | 2-11 | 33-51-16 | D13244 | | E | | SM00051 | | S | | 150-199 |
| 634 | 20 | | PA | | 2-11 | 33-51-16 | D13244 | | D | | GD04618 | | D.. | E | 050-099 |
| 634 | 20 | | PA | | 3-0 | 33-51-16 | D13244 | | D | | GD04618 | | D.. | E | 150-199 |
| 635 | 22 | | PA | | 2-9 | 33-51-16 | D13244 | | L | | SM00043 | | S | | 050-099 |
| 635 | 22 | | PA | | 3-3 | 33-51-16 | D13244 | | L | | SM00043 | | S | | 150-199 |
| 636 | 22 | | PA | | 2-9 | 33-51-16 | D13244 | | K | | SM00044 | | S | | 050-099 |
| 636 | 22 | | PA | | 3-3 | 33-51-16 | D13244 | | K | | SM00044 | | S | | 150-199 |
| 637 | 20 | | PA | | 2-9 | 33-51-16 | D13244 | | A | | SM00045 | | S | | 050-099 |
| 637 | 20 | | PA | | 3-3 | 33-51-16 | D13244 | | A | | SM00045 | | S | | 150-199 |
| 638 | 20 | | PA | | 2-3 | 33-51-17 | D13260 | | A | | SM00032 | | S | | 050-099 |
| 638 | 20 | | PA | | 0-3 | 33-51-17 | D13260 | | A | | SM00032 | | S | | 150-199 |
| 639 | 20 | | PA | | 2-3 | 33-51-17 | D13260 | | B | | SM00033 | | S | | 050-099 |
| 639 | 20 | | PA | | 0-3 | 33-51-17 | D13260 | | B | | SM00033 | | S | | 150-199 |
| 640 | 20 | | PA | | 2-3 | 33-51-17 | D13260 | | C | | SM00034 | | S | | 050-099 |
| 640 | 20 | | PA | | 0-3 | 33-51-17 | D13260 | | C | | SM00034 | | S | | 150-199 |
| 641 | 20 | | PA | | 2-3 | 33-51-17 | D13260 | | D | | SM00035 | | S | | 050-099 |
| 641 | 20 | | PA | | 0-3 | 33-51-17 | D13260 | | D | | SM00035 | | S | | 150-199 |
| 648 | 20 | | PA | | 2-2 | 33-51-11 | SM00045 | | | S | D00170 | | 2 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0790
Page 6
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0790 | 286T0790 | | | R AFT EMER LTG (continued) | | | | | | | | | | | | | |
| 648 | 20 | | PA | 0-7 | 33-51-11 | SM00045 | | | | | S | | D00170 | 2 | | | 150-199 |
| 649 | 22 | | PA | 2-2 | 33-51-11 | SM00043 | | | | | S | | D00170 | 4 | | | 050-099 |
| 649 | 22 | | PA | 0-7 | 33-51-11 | SM00043 | | | | | S | | D00170 | 4 | | | 150-199 |
| 650 | 22 | | PA | 2-2 | 33-51-11 | SM00044 | | | | | S | | D00170 | 3 | | | 050-099 |
| 650 | 22 | | PA | 0-7 | 33-51-11 | SM00044 | | | | | S | | D00170 | 3 | | | 150-199 |
| 651 | 22 | | PA | 1-5 | 33-51-11 | D01088 | | 4 | | | | | SM00041 | | S | | 050-099 |
| 651 | 22 | | PA | 0-3 | 33-51-11 | SM00041 | | | | | S | | D01088 | 4 | | | 150-199 |
| 652 | 20 | | PA | 1-5 | 33-51-11 | D01088 | | 2 | | | | | SM00042 | | S | | 050-099 |
| 652 | 20 | | PA | 0-7 | 33-51-11 | SM00042 | | | | | S | | D01088 | 2 | | | 150-199 |
| 655 | 20 | | PA | 14-3 | 33-51-16 | D13236 | | | B | | | | SM00046 | | S | | 050-099 |
| 655 | 20 | | PA | 3-1 | 33-51-16 | D13236 | | | B | | | | SM00046 | | S | | 150-199 |
| 656 | 20 | | PA | 14-3 | 33-51-16 | D13236 | | | A | | | | SM00047 | | S | | 050-099 |
| 656 | 20 | | PA | 3-1 | 33-51-16 | D13236 | | | A | | | | SM00047 | | S | | 150-199 |
| 657 | 20 | | PA | 14-3 | 33-51-16 | D13236 | | | D | | | | SM00051 | | S | | 050-099 |
| 657 | 20 | | PA | 3-1 | 33-51-16 | SM00051 | | | | S | | | D13236 | D | | | 150-199 |
| 658 | 20 | | PA | 38-2 | 33-51-16 | D12082 | | | C | | | | SM00052 | | S | | 050-099 |
| 658 | 20 | | PA | 42-1 | 33-51-16 | SM00052 | | | | S | | | D12082 | C | | | 150-199 |
| 659 | 20 | | PA | 38-2 | 33-51-16 | D12082 | | | D | | | | SM00051 | | S | | 050-099 |
| 659 | 20 | | PA | 42-1 | 33-51-16 | SM00051 | | | | S | | | D12082 | D | | | 150-199 |
| 660 | 20 | | PA | 14-3 | 33-51-16 | D13236 | | | C | | | | SM00052 | | S | | 050-099 |
| 660 | 20 | | PA | 3-1 | 33-51-16 | SM00052 | | | | S | | | D13236 | C | | | 150-199 |
| 661 | 20 | | PA | 28-7 | 33-51-16 | D12080 | | | C | | | | SM00052 | | S | | 050-099 |
| 661 | 20 | | PA | 38-8 | 33-51-16 | SM00052 | | | | S | | | D12080 | C | | | 150-199 |
| 662 | 20 | | PA | 28-7 | 33-51-16 | D12080 | | | D | | | | SM00051 | | S | | 050-099 |
| 662 | 20 | | PA | 38-8 | 33-51-16 | SM00051 | | | | S | | | D12080 | D | | | 150-199 |
| 663 | 20 | | PA | 29-10 | 33-51-14 | D13226 | | | D | | | | SM00051 | | S | | 050-099 |
| 664 | 20 | | PA | 29-10 | 33-51-14 | D13226 | | | C | | | | SM00052 | | S | | 050-099 |
| 665 | 20 | | PA | 29-10 | 33-51-14 | D13226 | | | B | | | | SM00046 | | S | | 050-099 |
| 666 | 20 | | PA | 29-10 | 33-51-14 | D13226 | | | A | | | | SM00047 | | S | | 050-099 |
| 667 | 20 | | PA | 41-0 | 33-51-16 | D12256 | | | A | | | | SM00047 | | S | | 050-099 |
| 668 | 20 | | PA | 41-0 | 33-51-16 | D12256 | | | B | | | | SM00046 | | S | | 050-099 |
| 669 | 20 | | PA | 41-0 | 33-51-16 | D12256 | | | C | | | | SM00052 | | S | | 050-099 |
| 670 | 20 | | PA | 41-0 | 33-51-16 | D12256 | | | D | | | | SM00051 | | S | | 050-099 |
| 675 | 20 | | PA | 28-7 | 33-51-16 | D12080 | | | A | | | | SM00047 | | S | | 050-099 |
| 675 | 20 | | PA | 38-8 | 33-51-16 | D12080 | | | A | | | | SM00047 | | S | | 150-199 |
| 676 | 20 | | PA | 28-7 | 33-51-16 | D12080 | | | B | | | | SM00046 | | S | | 050-099 |
| 676 | 20 | | PA | 38-8 | 33-51-16 | D12080 | | | B | | | | SM00046 | | S | | 150-199 |
| 677 | 20 | | PA | 38-2 | 33-51-16 | D12082 | | | B | | | | SM00046 | | S | | 050-099 |
| 677 | 20 | | PA | 42-1 | 33-51-16 | D12082 | | | B | | | | SM00046 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0790

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0790 | 286T0790 | | | R AFT EMER LTG (continued) | | | | | | | | | | | | | |
| 678 | 20 | | PA | 38-2 | 33-51-16 | D12082 | | A | | | | | SM00047 | | S | | 050-099 |
| 678 | 20 | | PA | 42-1 | 33-51-16 | D12082 | | A | | | | | SM00047 | | S | | 150-199 |
| A-A | | | | 0-0 | 52-71-11 | SP00672 | | | 9 | | | | S00206 | RED | | | ALL |
| A-B | | | | 0-0 | 52-71-11 | SP00674 | | | 9 | | | | S00206 | BLU | | | ALL |
| B-A | | | | 0-0 | 52-71-11 | SP00676 | | | 9 | | | | S00207 | RED | | | ALL |
| B-B | | | | 0-0 | 52-71-11 | SP00678 | | | 9 | | | | S00207 | BLU | | | ALL |
| C-A | | | | 0-0 | 52-71-11 | SP01972 | | | 9 | | | | S00213 | RED | | | ALL |
| C-B | | | | 0-0 | 52-71-11 | SP01974 | | | 9 | | | | S00213 | BLU | | | ALL |
| W0792 | 286T0792 | | | RETRACTABLE OVERHEAD CLOSETS-LEFT MID LAVS | | | | | | | | | | | | | |
| 002 | 18 | | PA | 4-10 | 33-26-11 | D00810 | | | 6 | | | | SM00001 | | 9 | | 150-199 |
| 003 | 20 | | PA | 42-5 | 33-26-21 | D13416 | | | 10 | | | | SP03676 | | 9 | | 150-199 |
| 005 | 16 | | PA | 11-11 | 38-13-11 | D13414 | | | 2 | | | | GD01554 | A.. | E | | 050-099 |
| 006 | 20 | | PA | 16-4 | 33-26-11 | D00810 | | | 1 | | | | GD04988 | A.. | E | | 150-199 |
| 007 | 20 | | PA | 42-5 | 33-26-21 | D13416 | | | 13 | | | | SP03626 | | 9 | | 150-199 |
| 008 | 20 | | PA | 42-5 | 33-26-21 | D13416 | | | 14 | | | | SP03626 | | 9 | | 150-199 |
| 011 | 18 | | PA | 0-6 | 33-26-11 | D13414 | | | 6 | | | | SM00001 | | 9 | | 050-099 |
| 011 | 18 | | PA | 0-6 | 33-26-11 | D00810 | | | 6 | | | | SM00001 | | 9 | | 275-299 |
| 018 | 20 | | PA | 4-7 | 33-26-11 | D13416 | | | 1 | | | | GD01952 | A.. | 2 | | 150-199 |
| 034 | 20 | | PA | 43-9 | 33-26-21 | D04326P | | | 15 | | | | D00810 | | 13 | | 050-099 |
| 034 | 20 | | PA | 18-2 | 33-26-21 | L00426 | | S | C | | * | | D00810 | | 13 | | 275-299 |
| 035 | 20 | | PA | 22-4 | 33-26-21 | SM00032 | | | 9 | | | | L00401 | P | C | | 150-199 |
| 035 | 20 | | PA | 54-4 | 33-26-21 | D04326P | | | 6 | | | | L00401 | P | C | * | 275-278 |
| 035 | 20 | | PA | 54-4 | 33-26-21 | D04326P | | | 6 | | | | L00401 | P | C | | 280-299 |
| 036 | 20 | | PA | 14-8 | 33-26-21 | L00401 | | P | C | | | | SM00054 | | S | | 050-099 |
| 036 | 20 | | PA | 29-10 | 33-26-21 | L00426 | | P | C | | * | | L00401 | P | C | * | 275-278 |
| 036 | 20 | | PA | 21-3 | 33-26-21 | L00426 | | P | C | | * | | D05070P | | 22 | | 280-299 |
| 037 | 20 | | PA | 14-8 | 33-26-21 | L00401 | | S | C | | | | SM00051 | | 9 | | 050-099 |
| 037 | 20 | | PA | 44-1 | 33-26-21 | L00401 | | S | C | | | | SP03704 | | 9 | | 150-199 |
| 037 | 20 | | PA | 29-10 | 33-26-21 | L00401 | | S | C | | | | L00426 | | S | C | 275-278 |
| 037 | 20 | | PA | 29-10 | 33-26-21 | L00401 | | S | C | | * | | L00426 | | S | C | 280-299 |
| 038 | 20 | | PA | 6-8 | 33-26-21 | GD01940 | | A.. | 2 | | | | L00401 | G | C | | 050-099 |
| 038 | 20 | | PA | 16-8 | 33-26-21 | GD00960 | | A.. | 2 | | | | L00401 | G | C | | 150-199 |
| 038 | 20 | | PA | 7-1 | 33-26-21 | GD01940 | | A.. | 2 | | | | L00401 | G | C | | 275-299 |
| 039 | 20 | | PA | 24-1 | 33-26-21 | D00810 | | | 10 | | | | D05070P | | 38 | | 275-299 |
| 042 | 20 | | PA | 7-10 | 33-26-21 | GD02544 | | A.. | 2 | | | | L00402 | G | C | | 275-299 |
| 043 | 20 | | PA | 54-4 | 33-26-21 | L00401 | | S | C | | * | | D04326P | | 15 | | 280-299 |
| 046 | 22 | | PA | 1-0 | 33-26-11 | D04326P | | | 4 | | | | SM00020 | | 9 | | 050-099 |
| 046 | 22 | | PA | 60-1 | 33-26-11 | D04326P | | | 4 | | | | SP03910 | | 9 | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0790
Page 8
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0792 | 286T0792 | | | RETRACTABLE OVERHEAD CLOSETS-LEFT MID LAVS (continued) | | | | | | | | | | | | | | |
| 046 | 22 | | PA | 51-9 | 33-26-11 | D04326P | | 4 | | | | | | SM00001 | | 9 | | 275-299 |
| 047 | 20 | | PA | 9-8 | 38-32-12 | D00810 | | 19 | | | | | | GD03860 | S.. | E | | 050-099 |
| 047 | 20 | | PA | 3-1 | 38-32-12 | D00810 | | 19 | | | | | | GD04848 | S.. | E | | 150-156, 162-165 |
| 047 | 20 | | PA | 3-1 | 38-32-16 | D00810 | | 19 | | | | | | GD04848 | S.. | E | | 157, 166-199 |
| 047 | 20 | | PA | 3-6 | 38-32-12 | D00810 | | 19 | | | | | | GD03860 | S.. | E | | 275-276 |
| 047 | 20 | | PA | 3-6 | 38-32-16 | D00810 | | 19 | | | | | | GD03860 | S.. | E | | 277-299 |
| 048 | 20 | | PA | 9-8 | 38-32-12 | D00810 | | 18 | | | | | | GD03918 | D.. | E | | 050-099 |
| 048 | 20 | | PA | 16-4 | 38-32-12 | D00810 | | 18 | | | | | | GD04988 | D.. | E | | 150-156, 162-165 |
| 048 | 20 | | PA | 16-4 | 38-32-16 | D00810 | | 18 | | | | | | GD04988 | D.. | E | | 157, 166-199 |
| 048 | 20 | | PA | 3-6 | 38-32-12 | D00810 | | 18 | | | | | | GD03918 | D.. | E | | 275-276 |
| 048 | 20 | | PA | 3-6 | 38-32-16 | D00810 | | 18 | | | | | | GD03918 | D.. | E | | 277-299 |
| 049 | 18 | | PA | 7-8 | 38-32-12 | D00810 | | 20 | DK | | | | | SM00026 | | S | | 050-099 |
| 049 | 18 | | PA | 25-5 | 38-32-12 | D00810 | | 20 | DK | | | | | SM00026 | | 9 | | 150-156, 162-165 |
| 049 | 18 | | PA | 25-5 | 38-32-16 | D00810 | | 20 | DK | | | | | SM00026 | | 9 | | 157, 166-199 |
| 049 | 18 | | PA | 51-9 | 38-32-12 | D00810 | | 20 | DK | | | | | D04326P | 26 | DL | | 275-276 |
| 049 | 18 | | PA | 51-9 | 38-32-16 | D00810 | | 20 | DK | | | | | D04326P | 26 | DL | | 277-299 |
| 050 | 20 | | PA | 5-5 | 38-32-12 | D00810 | | 21 | | | | | | SM00052 | | S | | 050-099 |
| 050 | 20 | | PA | 29-1 | 38-32-12 | D00810 | | 21 | | | | | | SP03819 | | S | | 150-156, 162-165 |
| 050 | 20 | | PA | 29-1 | 38-32-16 | D00810 | | 21 | | | | | | SP03819 | | S | | 157, 166-199 |
| 050 | 20 | | PA | 24-1 | 38-32-12 | D00810 | | 21 | | | | | | D05070P | 25 | | | 275-276 |
| 050 | 20 | | PA | 24-1 | 38-32-16 | D00810 | | 21 | | | | | | D05070P | 25 | | | 277-299 |
| 051 | 22 | | PA | 57-10 | 38-32-12 | D04326P | | 17 | | | | | | D05070P | 26 | | | 050-099 |
| 051 | 20 | | PA | 67-7 | 38-32-12 | D04326P | | 17 | | | | | | D05070P | 26 | | | 150-156, 162-165 |
| 051 | 20 | | PA | 67-7 | 38-32-16 | D04326P | | 17 | | | | | | D05070P | 26 | | | 157, 166-199 |
| 051 | 20 | | PA | 67-6 | 38-32-12 | D04326P | | 17 | | | | | | D05070P | 26 | | | 275-276 |
| 051 | 20 | | PA | 67-6 | 38-32-16 | D04326P | | 17 | | | | | | D05070P | 26 | | | 277-299 |
| 052 | 20 | | PA | 11-11 | 33-26-11 | D13414 | | 1 | | | | | | GD01554 | A.. | E | | 050-099 |
| 052 | 20 | | PA | 3-6 | 33-26-11 | D00810 | | 1 | | | | | | GD03916 | A.. | E | | 275-299 |
| 053 | 16 | | PA | 9-8 | 38-13-11 | D00810 | | 2 | | | | | | GD03916 | A.. | E | | 050-099 |
| 053 | 16 | | PA | 3-0 | 38-13-11 | D00810 | | 2 | | | | | | GD04864 | A.. | E | | 150-199 |
| 053 | 16 | | PA | 3-6 | 38-13-11 | D00810 | | 2 | | | | | | GD03916 | A.. | E | | 275-299 |
| 055 | 22 | | PA | 26-5 | 33-26-11 | SM00015 | | | 9 | | | | | D13414 | 15 | | | 050-099 |
| 055 | 22 | | PA | 51-9 | 33-26-11 | D00810 | | 15 | | | | | | D04326P | 3 | | | 275-299 |
| 056 | 20 | | PA | 7-8 | 33-26-11 | D00810 | | 17 | | | | | | SM00006 | | S | | 050-099 |
| 056 | 20 | | PA | 12-6 | 33-26-11 | D00810 | | 17 | | | | | | SM00006 | | S | | 275-299 |
| 057 | 16 | | PA | 63-0 | 38-13-11 | D04326P | | 21 | FL | | | | | D13414 | 8 | | | 050-099 |
| 057 | 16 | | PA | 67-6 | 38-13-11 | D04326P | | 21 | | | | | | D05070P | 23 | | | 275-299 |
| 058 | 16 | | PA | 43-9 | 38-13-11 | D04326P | | 23 | FL | | | | | D00810 | 8 | | | 050-099 |
| 058 | 16 | | PA | 25-5 | 38-13-11 | SM00021 | | | 9 | | | | | D00810 | 8 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0790

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|---------|--------|--------|------------------|---------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0792 | 286T0792 | | | RETRACTABLE OVERHEAD CLOSETS-LEFT MID LAVS (continued) | | | | | | | | | | | | | |
| 058 | 16 | PA | | 51-9 | 38-13-11 | D04326P | | 23 | | | D00810 | | 8 | | 275-299 | | |
| 059 | 22 | PA | | 33-9 | 33-26-11 | D04326P | | 2 | | | SM00001 | | 9 | | 150-199 | | |
| 059 | 22 | PA | | 67-6 | 33-26-11 | D04326P | | 2 | | | D05070P | | 21 | | 275-299 | | |
| 064 | 22 | PA | | 42-9 | 33-25-11 | D04326P | | 7 | | | SM00008 | | | S | 050-099 | | |
| 064 | 22 | PA | | 56-5 | 33-25-11 | D04326P | | 7 | | | SM00008 | | | S | 150-199 | | |
| 064 | 22 | PA | | 39-10 | 33-25-11 | D04326P | | 7 | | | SM00008 | | | S | 275-299 | | |
| 066 | 22 | PA | | 26-5 | 33-25-11 | D13414 | | 7 | | | SM00053 | | | S | 050-099 | | |
| 066 | 22 | PA | | 33-10 | 33-25-11 | D10570 | | 7 | | | SP00327 | | | S | 150-199 | | |
| 066 | 22 | PA | | 25-5 | 33-25-11 | D00810 | | 7 | | | SP00329 | | | S | 275-299 | | |
| 067 | 22 | PA | | 27-3 | 33-25-11 | D13414 | | 9 | | | SM00008 | | | S | 050-099 | | |
| 067 | 22 | PA | | 19-5 | 33-25-11 | D10570 | | 9 | | | SM00008 | | | S | 150-199 | | |
| 067 | 22 | PA | | 12-6 | 33-25-11 | D00810 | | 9 | | | SM00008 | | | S | 275-299 | | |
| 068 | 22 | PA | | 13-7 | 33-25-11 | D13414 | | 25 | | | D05070P | | 17 | | 050-099 | | |
| 068 | 22 | PA | | 33-10 | 33-25-11 | D10570 | | 25 | | | SP03696 | | 9 | | 150-199 | | |
| 068 | 22 | PA | | 24-11 | 33-25-11 | D00810 | | 25 | | | SP00570 | | | S | 275-299 | | |
| 069 | 20 | PA | | 12-0 | 33-25-11 | D13414 | | 26 | | | GD02552 | | D.. | E | 050-099 | | |
| 069 | 20 | PA | | 3-11 | 33-25-11 | D10570 | | 26 | | | GD04918 | | D.. | E | 150-199 | | |
| 069 | 20 | PA | | 3-6 | 33-25-11 | D00810 | | 26 | | | GD03918 | | D.. | E | 275-299 | | |
| 071 | 20 | PA | | 11-9 | 33-26-21 | L00426 | | | P | C | * | L00402 | | P | C | 275-299 | |
| 072 | 20 | PA | | 6-7 | 33-26-21 | GD01944 | | | A.. | 2 | | L00426 | | G | C | 275-299 | |
| 076 | 22 | PA | | 22-1 | 33-25-11 | SM00008 | | | | S | | D05070P | | 19 | | 050-099 | |
| 076 | 22 | PA | | 12-3 | 33-25-11 | SM00008 | | | | S | | D05070P | | 19 | | 150-199 | |
| 076 | 22 | PA | | 28-3 | 33-25-11 | SM00008 | | | | S | | D05070P | | 19 | | 275-299 | |
| 088 | 22 | PA | | 42-4 | 33-26-11 | SM00020 | | | | 9 | | SM00019 | | 9 | | 050-099 | |
| 089 | 22 | PA | | 61-8 | 33-26-11 | SM00020 | | | | 9 | | SM00001 | | 9 | | 050-099 | |
| 090 | 20 | PA | | 37-1 | 33-24-11 | D04326P | | 13 | | | SM00014 | | | S | 050-099 | | |
| 090 | 20 | PA | | 60-1 | 33-24-11 | SP01586 | | | | 9 | | D04326P | | 13 | | 150-199 | |
| 090 | 20 | PA | | 51-9 | 33-24-11 | D00810 | | 12 | | | D04326P | | 13 | | 275-299 | | |
| 091 | 20 | PA | | 7-8 | 33-24-11 | D00810 | | 12 | | | SM00014 | | | S | 050-099 | | |
| 091 | 20 | PA | | 29-1 | 33-24-11 | D00810 | | 12 | | | SP03578 | | 9 | | 150-199 | | |
| 095 | 20 | PA | | 37-1 | 33-26-11 | SM00006 | | | | S | | D04326P | | 19 | | 050-099 | |
| 095 | 20 | PA | | 60-1 | 33-26-11 | D04326P | | 19 | | | SP03668 | | 9 | | 150-199 | | |
| 095 | 20 | PA | | 39-10 | 33-26-11 | SM00006 | | | | S | | D04326P | | 19 | | 275-299 | |
| 096 | 20 | PA | | 28-3 | 33-26-11 | SM00006 | | | | S | | D05070P | | 36 | | 275-299 | |
| 098 | 20 | PA | | 11-9 | 33-26-21 | L00402 | | | | S | C | * | L00426 | | S | C | 275-299 |
| 099 | 18 | PA | | 57-10 | 38-32-12 | D04326P | | 24 | DL | | D05070P | | 24 | DK | 050-099 | | |
| 099 | 18 | PA | | 67-7 | 38-32-12 | D04326P | | 41 | DL | | D05070P | | 24 | DK | 150-156, 162-165 | | |
| 099 | 18 | PA | | 67-7 | 38-32-16 | D04326P | | 41 | DL | | D05070P | | 24 | DK | 157, 166-199 | | |
| 099 | 18 | PA | | 67-6 | 38-32-12 | D04326P | | 24 | DL | | D05070P | | 24 | DK | 275-276 | | |

WIRE LIST

D280T132

91-21-11

Section W0790

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|--|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0792 | 286T0792 | | | RETRACTABLE OVERHEAD CLOSETS-LEFT MID LAVS (continued) | | | | | | | | | | | | |
| 099 | 18 | | PA | 67-6 | 38-32-16 | D04326P | 24 | DL | | D05070P | 24 | DK | | 277-299 | | |
| 101 | 20 | | PA | 9-8 | 33-26-11 | D00810 | 1 | | | GD03916 | A.. | E | | 050-099 | | |
| 106 | 18 | | PA | 1-6 | 33-26-11 | SM00019 | | 9 | | D00810 | 6 | | | 050-099 | | |
| 107 | 22 | | PA | 28-0 | 33-25-11 | D13416 | 7 | | | SP00329 | | S | | 150-199 | | |
| 109 | 22 | | PA | 13-6 | 33-25-11 | D13416 | 9 | | | SM00008 | | S | | 150-199 | | |
| 111 | 18 | | PA | 37-1 | 38-32-12 | D04326P | 26 | DL | | SM00026 | | S | | 050-099 | | |
| 111 | 18 | | PA | 56-5 | 38-32-12 | D04326P | 42 | DL | | SM00026 | 9 | | | 150-156, 162-165 | | |
| 111 | 18 | | PA | 56-5 | 38-32-16 | D04326P | 42 | DL | | SM00026 | 9 | | | 157, 166-199 | | |
| 112 | 20 | | PA | 26-5 | 33-24-11 | D13414 | 12 | | | SM00014 | | S | | 050-099 | | |
| 112 | 20 | | PA | 42-5 | 33-24-11 | D13416 | 12 | | | SP03578 | 9 | | | 150-199 | | |
| 114 | 20 | | PA | 18-2 | 38-32-12 | D05070P | 25 | | | SM00052 | | S | | 050-099 | | |
| 114 | 20 | | PA | 41-2 | 38-32-12 | D05070P | 25 | | | SP03819 | | S | | 150-156, 162-165 | | |
| 114 | 20 | | PA | 41-2 | 38-32-16 | D05070P | 25 | | | SP03819 | | S | | 157, 166-199 | | |
| 115 | 22 | | PA | 7-8 | 33-26-11 | SM00015 | | 9 | | D00810 | 15 | | | 050-099 | | |
| 117 | 20 | | PA | 26-5 | 33-26-11 | SM00006 | | S | | D13414 | 17 | | | 050-099 | | |
| 125 | 22 | | PA | 28-0 | 33-25-11 | D13416 | 25 | | | SP00570 | | S | | 150-199 | | |
| 126 | 20 | | PA | 4-7 | 33-25-11 | D13416 | 26 | | | GD01952 | D.. | 2 | | 150-199 | | |
| 133 | 20 | | PA | 37-1 | 33-26-11 | D04326P | 3 | | | SM00015 | | 9 | | 050-099 | | |
| 134 | 16 | | PA | 56-5 | 38-13-11 | D04326P | 40 | | | SM00021 | | 9 | | 150-199 | | |
| 136 | 20 | | PA | 68-10 | 33-24-11 | D04326P | 25 | | | D13416 | 30 | | | 150-199 | | |
| 137 | 20 | | PA | 68-10 | 33-24-11 | D04326P | 35 | | | D13416 | 32 | | | 150-199 | | |
| 138 | 20 | | PA | 24-7 | 25-42-11 | D13486 | 10 | | | SM00003 | | 9 | | 050-099 | | |
| 138 | 20 | | PA | 36-8 | 25-42-11 | SM00003 | | 9 | | SM00023 | | 9 | | 150-199 | | |
| 141 | 16 | | PA | 29-11 | 38-13-11 | SP00491 | | 9 | | SM00021 | | 9 | | 150-199 | | |
| 142 | 20 | | PA | 4-7 | 38-32-12 | D13416 | 18 | | | GD01952 | D.. | 2 | | 150-156, 162-165 | | |
| 142 | 20 | | PA | 4-7 | 38-32-16 | D13416 | 18 | | | GD01952 | D.. | 2 | | 157, 166-199 | | |
| 143 | 20 | | PA | 4-7 | 38-32-12 | D13416 | 19 | | | GD01952 | S.. | 2 | | 150-156, 162-165 | | |
| 143 | 20 | | PA | 4-7 | 38-32-16 | D13416 | 19 | | | GD01952 | S.. | 2 | | 157, 166-199 | | |
| 144 | 20 | | PA | 42-5 | 38-32-12 | D13416 | 20 | | | SP03818 | | S | | 150-156, 162-165 | | |
| 144 | 20 | | PA | 42-5 | 38-32-16 | D13416 | 20 | | | SP03818 | | S | | 157, 166-199 | | |
| 145 | 20 | | PA | 42-5 | 38-32-12 | D13416 | 21 | | | SP03819 | | S | | 150-156, 162-165 | | |
| 145 | 20 | | PA | 42-5 | 38-32-16 | D13416 | 21 | | | SP03819 | | S | | 157, 166-199 | | |
| 146 | 18 | | PA | 29-11 | 38-32-12 | SM00026 | | 9 | | SP03818 | | S | | 150-156, 162-165 | | |
| 146 | 18 | | PA | 29-11 | 38-32-16 | SM00026 | | 9 | | SP03818 | | S | | 157, 166-199 | | |
| 147 | 20 | | PA | 6-1 | 25-42-11 | D13480 | 10 | | | SM00003 | | 9 | | 050-099 | | |
| 147 | 20 | | PA | 4-5 | 25-42-11 | D13480 | 10 | | | SM00003 | | 9 | | 150-199 | | |
| 147 | 20 | | PA | 12-6 | 25-42-11 | D00810 | 29 | | | SM00003 | | 9 | | 275-299 | | |
| 148 | 20 | | PA | 7-0 | 25-42-11 | D13490 | 10 | | | SM00023 | | 9 | | 150-199 | | |
| 149 | 20 | | PA | 14-7 | 25-42-11 | D13488 | 10 | | | SM00023 | | 9 | | 150-199 | | |

WIRE LIST

D280T132

91-21-11

Section W0790

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|---------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0792 | 286T0792 | | | RETRACTABLE OVERHEAD CLOSETS-LEFT MID LAVS (continued) | | | | | | | | | | | | |
| 149 | 20 | | PA | | 28-3 | 25-42-11 | D05070P | | | | | | | | 9 | 275-299 |
| 150 | 16 | | PA | | 42-5 | 38-13-11 | D13416 | | | | | | | | 9 | 150-199 |
| 151 | 16 | | PA | | 4-7 | 38-13-11 | D13416 | | | | | | A.. | 2 | | 150-199 |
| 152 | 20 | | PA | | 37-1 | 25-42-11 | D04326P | | | | | | | | 9 | 050-099 |
| 152 | 20 | | PA | | 33-9 | 25-42-11 | D04326P | | | | | | | | 9 | 150-199 |
| 152 | 20 | | PA | | 39-10 | 25-42-11 | D04326P | | | | | | | | 9 | 275-299 |
| 153 | 20 | | PA | | 42-2 | 26-13-11 | D04326P | | | | | | | | 1 | 050-099 |
| 153 | 20 | | PA | | 37-1 | 26-13-11 | SP03602 | | | 9 | | | | | 1 | 150-199 |
| 154 | 20 | | PA | | 42-2 | 26-13-11 | D13480 | | | | | | | | 32 | 050-099 |
| 154 | 20 | | PA | | 37-1 | 26-13-11 | D13480 | | | | | | | | 9 | 150-199 |
| 155 | 20 | | PA | | 42-2 | 26-13-11 | D13480 | | | | | | | | 33 | 050-099 |
| 155 | 20 | | PA | | 37-1 | 26-13-11 | D13480 | | | | | | | | 9 | 150-199 |
| 156 | 20 | | PA | | 42-2 | 26-13-11 | D13480 | | | | | | | | 34 | 050-099 |
| 156 | 20 | | PA | | 37-1 | 26-13-11 | D13480 | | | | | | | | 9 | 150-199 |
| 157 | 20 | | PA | | 29-11 | 26-13-11 | SP03618 | | | 9 | | | | | 9 | 150-199 |
| 159 | 20 | | PA | | 43-5 | 26-13-11 | D13488 | | | | | | | | 9 | 150-199 |
| 160 | 20 | | PA | | 11-9 | 26-13-11 | D13486 | | | | | | | | 11 | 050-099 |
| 160 | 20 | | PA | | 49-5 | 26-13-11 | D13490 | | | | | | | | 9 | 150-199 |
| 161 | 20 | | PA | | 11-9 | 26-13-11 | D13486 | | | | | | | | 14 | 050-099 |
| 161 | 20 | | PA | | 20-6 | 26-13-11 | D13490 | | | | | | | | 9 | 150-199 |
| 162 | 20 | | PA | | 11-9 | 26-13-11 | D13486 | | | | | | | | 13 | 050-099 |
| 162 | 20 | | PA | | 20-6 | 26-13-11 | D13490 | | | | | | | | 9 | 150-199 |
| 163 | 20 | | PA | | 11-9 | 26-13-11 | D13486 | | | | | | | | 12 | 050-099 |
| 163 | 20 | | PA | | 20-6 | 26-13-11 | D13490 | | | | | | | | 9 | 150-199 |
| 164 | 20 | | PA | | 14-6 | 26-13-11 | D13488 | | | | | | | | 9 | 150-199 |
| 165 | 20 | | PA | | 14-6 | 26-13-11 | D13488 | | | | | | | | 9 | 150-199 |
| 166 | 20 | | PA | | 14-6 | 26-13-11 | D13488 | | | | | | | | 9 | 150-199 |
| 167 | 20 | | PA | | 29-11 | 26-13-11 | SP03614 | | | 9 | | | | | 9 | 150-199 |
| 168 | 20 | | PA | | 29-11 | 26-13-11 | SP03616 | | | 9 | | | | | 9 | 150-199 |
| 169 | 22 | | PA | | 24-2 | 33-25-11 | SP00572 | | | S | | | | | 7 | 050-099 |
| 169 | 22 | | PA | | 41-2 | 33-25-11 | D05070P | | | | | | | | S | 150-199 |
| 170 | 22 | | PA | | 41-2 | 33-25-11 | D05070P | | | 17 | | | | | 9 | 150-199 |
| 171 | 22 | | PA | | 1-6 | 33-25-11 | D00810 | | | 9 | | | | | S | 050-099 |
| 171 | 22 | | PA | | 29-1 | 33-25-11 | D00810 | | | 9 | | | | | 9 | 150-199 |
| 172 | 22 | | PA | | 19-1 | 33-25-11 | D00810 | | | 25 | | | | | S | 050-099 |
| 172 | 22 | | PA | | 29-1 | 33-25-11 | D00810 | | | 25 | | | | | S | 150-199 |
| 173 | 20 | | PA | | 9-8 | 33-25-11 | D00810 | | | 26 | | | D.. | E | | 050-099 |
| 173 | 20 | | PA | | 16-4 | 33-25-11 | D00810 | | | 26 | | | D.. | E | | 150-199 |
| 174 | 22 | | PA | | 7-8 | 33-25-11 | D00810 | | | 7 | | | | | S | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0790

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|-----|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W0792 | 286T0792 | | | RETRACTABLE OVERHEAD CLOSETS-LEFT MID LAVS (continued) | | | | | | | | | | | | | | |
| 174 | 22 | | PA | 29-1 | 33-25-11 | D00810 | | 7 | | | | | | SP03702 | | 9 | | 150-199 |
| 176 | 20 | | PA | 29-1 | 33-26-11 | SP03634 | | | 9 | | | | | D00810 | 15 | | | 150-199 |
| 177 | 20 | | PA | 69-8 | 33-26-11 | SP03632 | | | 9 | | | | | D13416 | 6 | | | 150-199 |
| 178 | 20 | | PA | 42-5 | 33-26-11 | SP03634 | | | 9 | | | | | D13416 | 15 | | | 150-199 |
| 179 | 22 | | PA | 34-5 | 33-26-11 | D05070P | | 32 | | | | | | SM00001 | | 9 | | 150-199 |
| 180 | 22 | | PA | 36-8 | 33-26-11 | D05070P | | 33 | | | | | | D00810 | 17 | | | 150-199 |
| 181 | 22 | | PA | 16-10 | 33-26-11 | D05070P | | 34 | | | | | | D13416 | 17 | | | 150-199 |
| 182 | 22 | | PA | 57-10 | 33-25-11 | D04326P | | 5 | | | | | | D05070P | 9 | | | 050-099 |
| 182 | 22 | | PA | 67-7 | 33-25-11 | D04326P | | 5 | | | | | | D05070P | 9 | | | 150-199 |
| 183 | 22 | | PA | 57-10 | 33-25-11 | D04326P | | 8 | | | | | | D05070P | 8 | | | 050-099 |
| 183 | 22 | | PA | 67-7 | 33-25-11 | D04326P | | 8 | | | | | | D05070P | 8 | | | 150-199 |
| 184 | 22 | | PA | 57-10 | 33-25-11 | D04326P | | 14 | | | | | | D05070P | 20 | | | 050-099 |
| 184 | 22 | | PA | 67-7 | 33-25-11 | D04326P | | 14 | | | | | | D05070P | 20 | | | 150-199 |
| 185 | 22 | | PA | 26-9 | 33-25-11 | D05070P | | 3 | | | | | | SP00570 | | S | | 150-199 |
| 187 | 20 | | PA | 11-9 | 33-26-21 | D13486 | | 11 | | | | | | D05070P | 28 | | | 050-099 |
| 187 | 20 | | PA | 23-9 | 33-26-21 | D13490 | | 11 | | | | | | D05070P | 28 | | | 150-199 |
| 188 | 20 | | PA | 11-9 | 33-26-21 | D13486 | | 12 | | | | | | D05070P | 15 | | | 050-099 |
| 188 | 20 | | PA | 49-5 | 33-26-21 | D13490 | | 12 | | | | | | SP03626 | | 9 | | 150-199 |
| 189 | 20 | | PA | 13-7 | 33-26-21 | D13414 | | 10 | | | | | | D05070P | 29 | | | 050-099 |
| 189 | 20 | | PA | 22-8 | 33-26-21 | D10570 | | 10 | | | | | | D05070P | 29 | | | 150-199 |
| 190 | 20 | | PA | 13-7 | 33-26-21 | D13414 | | 13 | | | | | | D05070P | 37 | | | 050-099 |
| 190 | 20 | | PA | 48-4 | 33-26-21 | D10570 | | 13 | | | | | | SP03624 | | 9 | | 150-199 |
| 191 | 20 | | PA | 26-2 | 33-26-21 | L01105 | | S | C | | | | | SM00051 | | 9 | | 050-099 |
| 191 | 20 | | PA | 47-6 | 33-26-21 | L01105 | | S | C | | | | | SP03704 | | 9 | | 150-199 |
| 192 | 20 | | PA | 4-2 | 33-26-21 | L01105 | | G | C | | | | | GD01748 | A.. | 2 | | 050-099 |
| 192 | 20 | | PA | 13-9 | 33-26-21 | L01105 | | G | C | | | | | GD01950 | A.. | 2 | | 150-199 |
| 193 | 20 | | PA | 37-1 | 33-26-21 | D04326P | | 43 | | | | | | SM00051 | | 9 | | 050-099 |
| 193 | 20 | | PA | 60-1 | 33-26-21 | D04326P | | 43 | | | | | | SP03704 | | 9 | | 150-199 |
| 194 | 20 | | PA | 6-1 | 33-26-21 | SM00051 | | | 9 | | | | | D13480 | 12 | | | 050-099 |
| 194 | 20 | | PA | 30-9 | 33-26-21 | D13480 | | 12 | | | | | | SP03704 | | 9 | | 150-199 |
| 195 | 20 | | PA | 6-1 | 33-26-21 | SM00032 | | | 9 | | | | | D13480 | 11 | | | 050-099 |
| 195 | 20 | | PA | 4-5 | 33-26-21 | D13480 | | 11 | | | | | | SM00032 | | 9 | | 150-199 |
| 196 | 20 | | PA | 7-8 | 33-26-21 | SM00032 | | | 9 | | | | | D00810 | 10 | | | 050-099 |
| 196 | 20 | | PA | 4-10 | 33-26-21 | D00810 | | 10 | | | | | | SM00032 | | 9 | | 150-199 |
| 197 | 20 | | PA | 29-1 | 33-26-21 | D00810 | | 13 | | | | | | SP03622 | | 9 | | 150-199 |
| 198 | 20 | | PA | 26-2 | 33-26-21 | L01105 | | P | C | | | | | SM00054 | | S | | 050-099 |
| 198 | 20 | | PA | 58-5 | 33-26-21 | L01105 | | P | C | | | | | L00401 | P | C | | 150-199 |
| 199 | 20 | | PA | 37-1 | 33-26-21 | D04326P | | 6 | | | | | | SM00032 | | 9 | | 050-099 |
| 199 | 20 | | PA | 33-9 | 33-26-21 | D04326P | | 6 | | | | | | SM00032 | | 9 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0790

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|-----|------------------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0792 | 286T0792 | | | RETRACTABLE OVERHEAD CLOSETS-LEFT MID LAVS (continued) | | | | | | | | | | | | | | |
| 201B | 22 | PB | A | | 43-9 | 23-31-14 | D04326P | | | | 10 | | | | SP01694 | S | 050-099 | |
| 201B | 22 | PB | A | | 60-1 | 23-31-14 | D04326P | | | | 10 | | | | SP01694 | S | 150-199 | |
| 201B | 22 | PB | A | | 59-9 | 23-31-14 | D04326P | | | | 10 | | | | SP01694 | S | 275-299 | |
| 201R | 22 | PB | A | | 0-0 | 23-31-14 | D04326P | | | | 9 | | | | SP01692 | S | ALL | |
| 202B | 22 | PB | B | | 21-10 | 23-31-14 | SP01694 | | | | | | S | | D00810 | 5 | 050-099 | |
| 202B | 22 | PB | B | | 29-1 | 23-31-14 | SP01694 | | | | | | S | | D00810 | 5 | 150-199 | |
| 202B | 22 | PB | B | | 25-5 | 23-31-14 | SP01694 | | | | | | S | | D00810 | 5 | 275-299 | |
| 202R | 22 | PB | B | | 0-0 | 23-31-14 | SP01692 | | | | | | S | | D00810 | 16 | ALL | |
| 206B | 22 | PB | IF | | 42-5 | 23-31-14 | D13416 | | | | 5 | | | | SP03592 | S | 150-199 | |
| 206R | 22 | PB | IF | | 0-0 | 23-31-14 | D13416 | | | | 16 | | | | SP03590 | S | 150-199 | |
| 207B | 22 | PB | IG | | 40-7 | 23-31-14 | D13414 | | | | 5 | | | | SP03592 | S | 050-099 | |
| 207B | 22 | PB | IG | | 48-4 | 23-31-14 | D10570 | | | | 5 | | | | SP03592 | S | 150-199 | |
| 207R | 22 | PB | IG | | 0-0 | 23-31-14 | D13414 | | | | 16 | | | | SP03590 | S | 050-099 | |
| 207R | 22 | PB | IG | | 0-0 | 23-31-14 | D10570 | | | | 16 | | | | SP03590 | S | 150-199 | |
| 208B | 22 | PB | IH | | 43-9 | 23-31-14 | D04326P | | | | 12 | | | | SP03592 | S | 050-099 | |
| 208B | 22 | PB | IH | | 60-1 | 23-31-14 | D04326P | | | | 12 | | | | SP03592 | S | 150-199 | |
| 208R | 22 | PB | IH | | 0-0 | 23-31-14 | D04326P | | | | 11 | | | | SP03590 | S | 050-099, 150-199 | |
| 501 | 22 | PA | | | 37-1 | 33-25-11 | D04326P | | | | 39 | | | | SM00053 | S | 050-099 | |
| 501 | 22 | PA | | | 26-9 | 33-25-11 | D05070P | | | | 5 | | | | SP03698 | S | 150-199 | |
| 503 | 22 | PA | | | 26-9 | 33-25-11 | D05070P | | | | 6 | | | | SP03696 | 9 | 150-199 | |
| 504 | 22 | PA | | | 21-3 | 33-25-11 | SM00053 | | | | | | S | | D05070P | 4 | 050-099 | |
| 504 | 22 | PA | | | 26-9 | 33-25-11 | D05070P | | | | 4 | | | | SP00572 | 9 | 150-199 | |
| 508 | 20 | PA | | | 0-7 | 33-26-21 | SM00032 | | | | | | 9 | | SM00054 | S | 050-099 | |
| 578 | 20 | PA | | | 48-4 | 33-24-11 | D10570 | | | | 12 | | | | SP01586 | 9 | 150-199 | |
| 644 | 20 | PA | | | 44-1 | 33-26-21 | L00401 | | | | | | S | C | SP03720 | 9 | 150-199 | |
| 645 | 20 | PA | | | 44-1 | 33-26-21 | L00401 | | | | | | P | C | SP03722 | 9 | 150-199 | |
| 666 | 20 | PA | | | 48-4 | 38-32-13 | D10570 | | | | 21 | | | | SP03814 | S | 150-156, 162-165 | |
| 666 | 20 | PA | | | 48-4 | 38-32-16 | D10570 | | | | 21 | | | | SP03814 | S | 157, 166-199 | |
| 667 | 20 | PA | | | 3-11 | 38-32-13 | D10570 | | | | 18 | | | | GD04918 | D.. | E | 150-156, 162-165 |
| 667 | 20 | PA | | | 3-11 | 38-32-16 | D10570 | | | | 18 | | | | GD04918 | D.. | E | 157, 166-199 |
| 668 | 20 | PA | | | 3-11 | 38-32-13 | D10570 | | | | 19 | | | | GD04920 | S.. | E | 150-156, 162-165 |
| 668 | 20 | PA | | | 3-11 | 38-32-16 | D10570 | | | | 19 | | | | GD04920 | S.. | E | 157, 166-199 |
| 669 | 20 | PA | | | 48-4 | 38-32-13 | D10570 | | | | 20 | | | | SP03816 | S | 150-156, 162-165 | |
| 669 | 20 | PA | | | 48-4 | 38-32-16 | D10570 | | | | 20 | | | | SP03816 | S | 157, 166-199 | |
| 671 | 22 | PA | | | 48-4 | 33-26-11 | D10570 | | | | 17 | | | | SP03668 | 9 | 150-199 | |
| 672 | 22 | PA | | | 48-4 | 33-26-11 | D10570 | | | | 6 | | | | SP03906 | 9 | 150-199 | |
| 673 | 22 | PA | | | 48-4 | 33-26-11 | D10570 | | | | 15 | | | | SP03908 | 9 | 150-199 | |
| 674 | 20 | PA | | | 3-11 | 33-26-11 | D10570 | | | | 1 | | | | GD04916 | A.. | E | 150-199 |
| 801 | 16 | PA | | | 48-4 | 38-13-11 | D10570 | | | | 8 | | | | SP00489 | 9 | 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W0790

Page 14

Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|----|-----|---|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO | | TY | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0792 | 286T0792 | | | | RETRACTABLE OVERHEAD CLOSETS-LEFT MID LAVS (continued) | | | | | | | | | | | |
| 802 | 16 | | PA | | 3-11 | 38-13-11 | D10570 | | 2 | | | GD04916 | A.. | E | | 150-199 |
| 814 | 20 | | PA | | 57-10 | SPARE | D04326P | | 38 | | | D05070P | 39 | | | 050-099 |
| 814 | 20 | | PA | | 67-7 | SPARE | D04326P | | 38 | | | D05070P | 39 | | | 150-199 |
| 814 | 20 | | PA | | 67-6 | SPARE | D04326P | | 38 | | | D05070P | 39 | | | 275-299 |
| 815 | 20 | | PA | | 57-10 | SPARE | D04326P | | 37 | | | D05070P | 31 | | | 050-099 |
| 815 | 20 | | PA | | 67-7 | SPARE | D04326P | | 37 | | | D05070P | 31 | | | 150-199 |
| 815 | 20 | | PA | | 67-6 | SPARE | D04326P | | 37 | | | D05070P | 31 | | | 275-299 |
| 891 | 20 | | PA | | 12-0 | 38-32-12 | D13414 | | 18 | | | GD02552 | D.. | E | | 050-099 |
| 892 | 20 | | PA | | 11-11 | 38-32-12 | D13414 | | 19 | | | GD01556 | S.. | E | | 050-099 |
| 893 | 20 | | PA | | 26-5 | 38-32-12 | D13414 | | 20 | | | SM00026 | | S | | 050-099 |
| 894 | 22 | | PA | | 23-4 | 38-32-12 | D13414 | | 21 | | | SM00052 | | S | | 050-099 |
| W0794 | 286T0794 | | | | RIGHT RETRACTABLE OVERHEAD CLOSETS AND/OR GASPER FAN | | | | | | | | | | | |
| 005 | 18 | | PA | | 44-0 | 21-24-11 | D05072P | | 5 | | | D01386 | 7 | | | 050-099 |
| 005 | 18 | | PA | | 40-3 | 21-24-11 | D05072P | | 5 | | | D01386 | 7 | | | 150-199 |
| 006 | 18 | | PA | | 44-0 | 21-24-11 | D05072P | | 6 | | | D01386 | 4 | | | 050-099 |
| 006 | 18 | | PA | | 40-3 | 21-24-11 | D05072P | | 6 | | | D01386 | 4 | | | 150-199 |
| 007 | 18 | | PA | | 44-0 | 21-24-11 | D05072P | | 7 | | | D01386 | 6 | | | 050-099 |
| 007 | 18 | | PA | | 40-3 | 21-24-11 | D05072P | | 7 | | | D01386 | 6 | | | 150-199 |
| 008 | 24 | | PK | | 44-0 | 21-24-11 | D05072P | | 8 | | | D01386 | 2 | | | 050-099 |
| 008 | 24 | | PK | | 40-3 | 21-24-11 | D05072P | | 8 | | | D01386 | 2 | | | 150-199 |
| 015 | 20 | | PA | | 6-0 | 21-24-11 | GD03802 | | | D.. | E | D01386 | 3 | | | 050-099 |
| 015 | 20 | | PA | | 8-0 | 21-24-11 | GD04992 | | | D.. | E | D01386 | 3 | | | 150-199 |
| 016 | 20 | | PA | | 6-0 | 21-24-11 | GD03804 | | | S.. | E | D01386 | 1 | | | 050-099 |
| 016 | 20 | | PA | | 8-0 | 21-24-11 | GD04848 | | | S.. | E | D01386 | 1 | | | 150-199 |
| W0798 | 286T0798 | | | | ANTI-COLLISION LT,FWD CABIN ZONE TEMP SENSOR | | | | | | | | | | | |
| 001 | 20 | | PA | | 1-0 | 21-65-11 | SM00001 | | | | S | D03998 | B | | | ALL |
| 002 | 20 | | PA | | 27-2 | 21-65-11 | SM00001 | | | | S | GD01924 | D.. | 2 | | 050-099 |
| 002 | 20 | | PA | | 14-0 | 21-65-11 | SM00001 | | | | S | GD01924 | D.. | 2 | | 150-199 |
| 002 | 20 | | PA | | 11-0 | 21-65-11 | SM00001 | | | | S | GD00960 | D.. | 2 | | 275-278 |
| 002 | 20 | | PA | | 9-4 | 21-65-11 | SM00001 | | | | S | GD01924 | D.. | 2 | | 280-299 |
| 004 | 20 | | PA | | 19-11 | 33-44-11 | D08080P | | 11 | | | D02664 | 1 | | | 050-099 |
| 004 | 20 | | PA | | 19-10 | 33-44-11 | D08080P | | 11 | | | D02664 | 1 | | | 150-199, 275-278 |
| 004 | 20 | | PA | | 19-5 | 33-44-11 | D08080P | | 11 | | | D02664 | 1 | | | 280-299 |
| 005 | 20 | | PA | | 1-11 | 33-44-11 | GD01924 | | | A.. | 2 | D02664 | 2 | | | 050-099 |
| 005 | 20 | | PA | | 2-3 | 33-44-11 | GD01924 | | | A.. | 2 | D02664 | 2 | | | 150-199, 275-278 |
| 005 | 20 | | PA | | 23-10 | 33-44-11 | GD01924 | | | A.. | 2 | D02664 | 2 | | | 280-299 |
| 006 | 18 | | PA | | 1-11 | 33-44-11 | GD01924 | | | S.. | 2 | D02664 | 3 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0790

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0798 | 286T0798 | | | ANTI-COLLISION LT,FWD CABIN ZONE TEMP SENSOR (continued) | | | | | | | | | | | |
| 006 | 18 | | PA | | 2-3 | 33-44-11 | GD01924 | S.. | 2 | | D02664 | | 3 | | 150-199, 275-278 |
| 006 | 18 | | PA | | 23-10 | 33-44-11 | GD01924 | S.. | 2 | | D02664 | | 3 | | 280-299 |
| 007 | 20 | | PA | | 0-7 | 21-65-11 | D13474 | | | B | SM00003 | | | S | 050-099 |
| 007 | 20 | | PA | | 1-0 | 21-65-11 | SM00003 | | | S | D13474 | | B | | 150-199, 275-299 |
| 008 | 20 | | PA | | 12-7 | 21-65-11 | SM00003 | | | S | GD01924 | | D.. | 2 | 050-099 |
| 008 | 20 | | PA | | 14-0 | 21-65-11 | SM00003 | | | S | GD01924 | | D.. | 2 | 150-199 |
| 008 | 20 | | PA | | 12-3 | 21-65-11 | SM00003 | | | S | GD01924 | | D.. | 2 | 275-278 |
| 008 | 20 | | PA | | 35-0 | 21-65-11 | SM00003 | | | S | GD01924 | | D.. | 2 | 280-299 |
| 201B | 22 | | PB | A | 36-1 | 21-51-12 | D08080P | | 1 | | D02796 | | 3 | | 050-099 |
| 201B | 22 | | PB | A | 31-9 | 21-51-12 | D08080P | | 1 | | D02796 | | 3 | | 150-199 |
| 201B | 22 | | PB | A | 57-3 | 21-51-12 | D08080P | | 1 | | D02796 | | 3 | | 275-278 |
| 201B | 22 | | PB | A | 48-6 | 21-51-12 | D08080P | | 1 | | D02796 | | 3 | | 280-299 |
| 201R | 22 | | PB | A | 0-0 | 21-51-12 | D08080P | | 2 | | D02796 | | 4 | | ALL |
| 202B | 24 | | PL | B | 36-1 | 21-61-21 | D08080P | | 3 | | D02796 | | 1 | | 050-099 |
| 202B | 24 | | PL | B | 31-9 | 21-61-21 | D08080P | | 3 | | D02796 | | 1 | | 150-199 |
| 202B | 24 | | PL | B | 57-3 | 21-61-21 | D08080P | | 3 | | D02796 | | 1 | | 275-278 |
| 202B | 24 | | PL | B | 48-6 | 21-61-21 | D08080P | | 3 | | D02796 | | 1 | | 280-299 |
| 202R | 24 | | PL | B | 0-0 | 21-61-21 | D08080P | | 4 | | D02796 | | 2 | | ALL |
| 203B | 24 | | PL | C | 32-5 | 21-61-21 | D08080P | | 5 | | D03984 | | 1 | | 050-099 |
| 203B | 24 | | PL | C | 31-6 | 21-61-21 | D08080P | | 5 | | D03984 | | 1 | | 150-199 |
| 203B | 24 | | PL | C | 31-8 | 21-61-21 | D08080P | | 5 | | D03984 | | 1 | | 275-299 |
| 203R | 24 | | PL | C | 0-0 | 21-61-21 | D08080P | | 6 | | D03984 | | 2 | | ALL |
| 205B | 20 | | PB | E | 36-1 | 21-65-11 | D08080P | | 9 | | D03998 | | A | | 050-099 |
| 205B | 20 | | PB | E | 31-8 | 21-65-11 | D08080P | | 9 | | D03998 | | A | | 150-199 |
| 205B | 20 | | PB | E | 57-3 | 21-65-11 | D08080P | | 9 | | D03998 | | A | | 275-278 |
| 205B | 20 | | PB | E | 48-6 | 21-65-11 | D08080P | | 9 | | D03998 | | A | | 280-299 |
| 205R | 20 | | PB | E | 0-0 | 21-65-11 | D08080P | | 10 | | SM00001 | | | S | ALL |
| 206B | 24 | | PL | IF | 21-4 | 21-61-61 | D08080P | | 19 | | D13466 | | 1 | | 050-099 |
| 206B | 24 | | PL | IF | 20-9 | 21-61-61 | D08080P | | 19 | | D13466 | | 1 | | 150-199 |
| 206B | 24 | | PL | IF | 20-5 | 21-61-61 | D08080P | | 19 | | D13466 | | 1 | | 275-278 |
| 206B | 24 | | PL | IF | 21-2 | 21-61-61 | D08080P | | 19 | | D13466 | | 1 | | 280-299 |
| 206R | 24 | | PL | IF | 0-0 | 21-61-61 | D08080P | | 18 | | D13466 | | 2 | | ALL |
| 208B | 20 | | PB | IH | 21-6 | 21-65-11 | D08080P | | 16 | | D13474 | | A | | 050-099 |
| 208B | 20 | | PB | IH | 31-8 | 21-65-11 | D08080P | | 16 | | D13474 | | A | | 150-199 |
| 208B | 20 | | PB | IH | 20-9 | 21-65-11 | D08080P | | 16 | | D13474 | | A | | 275-278 |
| 208B | 20 | | PB | IH | 22-2 | 21-65-11 | D08080P | | 16 | | D13474 | | A | | 280-299 |
| 208R | 20 | | PB | IH | 0-0 | 21-65-11 | D08080P | | 17 | | SM00003 | | | S | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0790
 Page 16 End
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0800 | 286T0800 | | | SPEAKERS AND PASS SIGNS,FWD LEFT | | | | | | | | | | | | | |
| 001 | 18 | PA | | 9-0 | 33-24-12 | D05182P | | 4 | | | | | SM00045 | | S | | 150-199 |
| 002 | 18 | PA | | 9-0 | 33-24-12 | D05182P | | 7 | | | | | SM00046 | | S | | 150-199 |
| 003 | 22 | PA | | 2-10 | 33-24-12 | SM00046 | | | S | | | | D03206 | 3 | | | 050-099 |
| 003 | 20 | PA | | 2-1 | 33-24-12 | SM00046 | | | S | | | | D03206 | 3 | | | 150-199 |
| 003 | 20 | PA | | 3-8 | 33-24-12 | SM00046 | | | S | | | | D03206 | 3 | | | 275-278 |
| 003 | 20 | PA | | 1-10 | 33-24-12 | SM00046 | | | S | | | | D03206 | 3 | | | 280-299 |
| 004 | 22 | PA | | 2-10 | 33-24-12 | SM00045 | | | S | | | | D03206 | 4 | | | 050-099 |
| 004 | 20 | PA | | 2-1 | 33-24-12 | SM00045 | | | S | | | | D03206 | 4 | | | 150-199 |
| 004 | 20 | PA | | 3-8 | 33-24-12 | SM00045 | | | S | | | | D03206 | 4 | | | 275-278 |
| 004 | 20 | PA | | 1-10 | 33-24-12 | SM00045 | | | S | | | | D03206 | 4 | | | 280-299 |
| 005 | 20 | PA | | 7-11 | 33-24-12 | GD02108 | | A.. | E | * | | | D03206 | 5 | | | 050-099 |
| 005 | 20 | PA | | 2-6 | 33-24-12 | GD05648 | | A.. | E | | | | D03206 | 5 | | | 150-199 |
| 005 | 20 | PA | | 1-9 | 33-24-12 | GD05156 | | A.. | E | | | | D03206 | 5 | | | 275-278 |
| 005 | 20 | PA | | 1-10 | 33-24-12 | GD05156 | | A.. | E | | | | D03206 | 5 | | | 280-299 |
| 006 | 18 | PA | | 3-2 | 33-24-12 | SM00045 | | | S | | | | SM00047 | | S | | 050-099 |
| 006 | 18 | PA | | 4-8 | 33-24-12 | SM00045 | | | S | | | | SM00049 | | S | | 150-199, 280-299 |
| 006 | 18 | PA | | 6-4 | 33-24-12 | SM00045 | | | S | | | | SM00049 | | S | | 275-278 |
| 007 | 18 | PA | | 3-2 | 33-24-12 | SM00046 | | | S | | | | SM00048 | | S | | 050-099 |
| 007 | 18 | PA | | 4-8 | 33-24-12 | SM00046 | | | S | | | | SM00050 | | S | | 150-199, 280-299 |
| 007 | 18 | PA | | 6-4 | 33-24-12 | SM00046 | | | S | | | | SM00050 | | S | | 275-278 |
| 008 | 22 | PA | | 3-0 | 33-24-12 | SM00048 | | | S | | | | D03208 | 3 | | | 050-099 |
| 008 | 20 | PA | | 2-1 | 33-24-12 | SM00050 | | | S | | | | D03208 | 3 | | | 150-199, 275-278 |
| 008 | 20 | PA | | 2-5 | 33-24-12 | SM00050 | | | S | | | | D03208 | 3 | | | 280-299 |
| 009 | 22 | PA | | 3-0 | 33-24-12 | SM00047 | | | S | | | | D03208 | 4 | | | 050-099 |
| 009 | 20 | PA | | 2-1 | 33-24-12 | SM00049 | | | S | | | | D03208 | 4 | | | 150-199, 275-278 |
| 009 | 20 | PA | | 2-5 | 33-24-12 | SM00049 | | | S | | | | D03208 | 4 | | | 280-299 |
| 010 | 20 | PA | | 6-0 | 33-24-12 | GD02108 | | A.. | E | * | | | D03208 | 5 | | | 050-099 |
| 010 | 20 | PA | | 2-6 | 33-24-12 | GD05648 | | A.. | E | | | | D03208 | 5 | | | 150-199 |
| 010 | 20 | PA | | 3-3 | 33-24-12 | GD05156 | | A.. | E | | | | D03208 | 5 | | | 275-299 |
| 011 | 18 | PA | | 8-2 | 33-24-12 | SM00047 | | | S | | | | SM00053 | | S | | 050-099 |
| 012 | 18 | PA | | 8-2 | 33-24-12 | SM00048 | | | S | | | | SM00054 | | S | | 050-099 |
| 013 | 22 | PA | | 3-11 | 33-24-12 | SM00048 | | | S | | | | D03210 | 3 | | | 050-099 |
| 013 | 20 | PA | | 1-8 | 33-24-12 | SM00050 | | | S | | | | D03210 | 3 | | | 150-199, 275-278 |
| 013 | 20 | PA | | 2-0 | 33-24-12 | SM00050 | | | S | | | | D03210 | 3 | | | 280-299 |
| 014 | 22 | PA | | 3-11 | 33-24-12 | SM00047 | | | S | | | | D03210 | 4 | | | 050-099 |
| 014 | 20 | PA | | 1-8 | 33-24-12 | SM00049 | | | S | | | | D03210 | 4 | | | 150-199, 275-278 |
| 014 | 20 | PA | | 2-0 | 33-24-12 | SM00049 | | | S | | | | D03210 | 4 | | | 280-299 |
| 015 | 20 | PA | | 4-1 | 33-24-12 | GD02108 | | A.. | E | | | | D03210 | 5 | | | 050-099 |
| 015 | 20 | PA | | 4-2 | 33-24-12 | GD02108 | | A.. | E | | | | D03210 | 5 | | | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0800 | 286T0800 | | | SPEAKERS AND PASS SIGNS,FWD LEFT (continued) | | | | | | | | | | | |
| 015 | 20 | | PA | | 4-5 | 33-24-12 | GD02108 | A.. | E | | D03210 | | 5 | | 280-299 |
| 016 | 18 | | PA | | 5-0 | 33-24-12 | SM00049 | | S | | SM00053 | | | S | 150-199, 275-278 |
| 016 | 18 | | PA | | 5-3 | 33-24-12 | SM00049 | | S | | SM00053 | | | S | 280-299 |
| 017 | 18 | | PA | | 5-0 | 33-24-12 | SM00050 | | S | | SM00054 | | | S | 150-199, 275-278 |
| 017 | 18 | | PA | | 5-3 | 33-24-12 | SM00050 | | S | | SM00054 | | | S | 280-299 |
| 018 | 22 | | PA | | 3-2 | 33-24-12 | SM00054 | | S | | D03212 | | 3 | | 050-099 |
| 018 | 20 | | PA | | 1-8 | 33-24-12 | SM00054 | | S | | D03212 | | 3 | | 150-199, 275-278 |
| 018 | 20 | | PA | | 1-10 | 33-24-12 | SM00054 | | S | | D03212 | | 3 | | 280-299 |
| 019 | 22 | | PA | | 3-2 | 33-24-12 | SM00053 | | S | | D03212 | | 4 | | 050-099 |
| 019 | 20 | | PA | | 1-8 | 33-24-12 | SM00053 | | S | | D03212 | | 4 | | 150-199, 275-278 |
| 019 | 20 | | PA | | 1-10 | 33-24-12 | SM00053 | | S | | D03212 | | 4 | | 280-299 |
| 020 | 20 | | PA | | 1-8 | 33-24-12 | GD02108 | A.. | E | | D03212 | | 5 | | 050-099, 150-199, 275-278 |
| 020 | 20 | | PA | | 2-0 | 33-24-12 | GD02108 | A.. | E | | D03212 | | 5 | | 280-299 |
| 023 | 22 | | PA | | 1-7 | 33-24-12 | SM00054 | | S | | D03214 | | 3 | | 050-099 |
| 023 | 20 | | PA | | 3-2 | 33-24-12 | SM00054 | | S | | D03214 | | 3 | | 150-199 |
| 023 | 20 | | PA | | 2-9 | 33-24-12 | SM00054 | | S | | D03214 | | 3 | | 275-278 |
| 023 | 20 | | PA | | 2-10 | 33-24-12 | SM00054 | | S | | D03214 | | 3 | | 280-299 |
| 024 | 22 | | PA | | 1-7 | 33-24-12 | SM00053 | | S | | D03214 | | 4 | | 050-099 |
| 024 | 20 | | PA | | 3-2 | 33-24-12 | SM00053 | | S | | D03214 | | 4 | | 150-199 |
| 024 | 20 | | PA | | 2-9 | 33-24-12 | SM00053 | | S | | D03214 | | 4 | | 275-278 |
| 024 | 20 | | PA | | 2-10 | 33-24-12 | SM00053 | | S | | D03214 | | 4 | | 280-299 |
| 025 | 20 | | PA | | 4-1 | 33-24-12 | GD02108 | A.. | E | | D03214 | | 5 | | 050-099, 150-199, 280-299 |
| 025 | 20 | | PA | | 3-8 | 33-24-12 | GD02108 | A.. | E | | D03214 | | 5 | | 275-278 |
| 026 | 18 | | PA | | 6-4 | 33-24-12 | SM00053 | | S | | SM00057 | | | S | 050-099 |
| 026 | 18 | | PA | | 6-0 | 33-24-12 | SM00053 | | S | | SM00057 | | | S | 150-199, 275-278 |
| 026 | 18 | | PA | | 7-0 | 33-24-12 | SM00053 | | S | | SM00057 | | | S | 280-299 |
| 027 | 18 | | PA | | 6-4 | 33-24-12 | SM00054 | | S | | SM00058 | | | S | 050-099 |
| 027 | 18 | | PA | | 6-0 | 33-24-12 | SM00054 | | S | | SM00058 | | | S | 150-199, 275-278 |
| 027 | 18 | | PA | | 7-0 | 33-24-12 | SM00054 | | S | | SM00058 | | | S | 280-299 |
| 028 | 22 | | PA | | 3-1 | 33-24-12 | SM00058 | | S | | D03216 | | 3 | | 050-099 |
| 028 | 20 | | PA | | 1-11 | 33-24-12 | SM00058 | | S | | D03216 | | 3 | | 150-199 |
| 028 | 20 | | PA | | 1-10 | 33-24-12 | SM00058 | | S | | D03216 | | 3 | | 275-278 |
| 028 | 20 | | PA | | 3-3 | 33-24-12 | SM00058 | | S | | D03216 | | 3 | | 280-299 |
| 029 | 22 | | PA | | 3-1 | 33-24-12 | SM00057 | | S | | D03216 | | 4 | | 050-099 |
| 029 | 20 | | PA | | 1-11 | 33-24-12 | SM00057 | | S | | D03216 | | 4 | | 150-199 |
| 029 | 20 | | PA | | 1-10 | 33-24-12 | SM00057 | | S | | D03216 | | 4 | | 275-278 |
| 029 | 20 | | PA | | 3-3 | 33-24-12 | SM00057 | | S | | D03216 | | 4 | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0800 | 286T0800 | | | SPEAKERS AND PASS SIGNS,FWD LEFT (continued) | | | | | | | | | | | | |
| 030 | 20 | | PA | 4-5 | 33-24-12 | GD02112 | A.. | E | | D03216 | | 5 | | 050-099 | | |
| 030 | 20 | | PA | 4-4 | 33-24-12 | GD02112 | A.. | E | | D03216 | | 5 | | 150-199 | | |
| 030 | 20 | | PA | 4-3 | 33-24-12 | GD02112 | A.. | E | | D03216 | | 5 | | 275-278 | | |
| 030 | 20 | | PA | 4-9 | 33-24-12 | GD02112 | A.. | E | | D03216 | | 5 | | 280-299 | | |
| 033 | 22 | | PA | 1-10 | 33-24-12 | SM00058 | | S | | D03218 | | 3 | | 050-099 | | |
| 033 | 20 | | PA | 3-1 | 33-24-12 | SM00058 | | S | | D03218 | | 3 | | 150-199, 275-278 | | |
| 033 | 20 | | PA | 2-1 | 33-24-12 | SM00058 | | S | | D03218 | | 3 | | 280-299 | | |
| 034 | 22 | | PA | 1-10 | 33-24-12 | SM00057 | | S | | D03218 | | 4 | | 050-099 | | |
| 034 | 20 | | PA | 3-1 | 33-24-12 | SM00057 | | S | | D03218 | | 4 | | 150-199, 275-278 | | |
| 034 | 20 | | PA | 2-1 | 33-24-12 | SM00057 | | S | | D03218 | | 4 | | 280-299 | | |
| 035 | 20 | | PA | 1-9 | 33-24-12 | GD02112 | A.. | E | | D03218 | | 5 | | 050-099 | | |
| 035 | 20 | | PA | 1-10 | 33-24-12 | GD02112 | A.. | E | | D03218 | | 5 | | 150-199, 275-278 | | |
| 035 | 20 | | PA | 1-11 | 33-24-12 | GD02112 | A.. | E | | D03218 | | 5 | | 280-299 | | |
| 036 | 18 | | PA | 5-5 | 33-24-12 | SM00057 | | S | | SM00061 | | | S | 050-099, 280-299 | | |
| 036 | 18 | | PA | 6-1 | 33-24-12 | SM00057 | | S | | SM00061 | | | S | 150-199, 275-278 | | |
| 037 | 18 | | PA | 5-5 | 33-24-12 | SM00058 | | S | | SM00062 | | | S | 050-099, 280-299 | | |
| 037 | 18 | | PA | 6-1 | 33-24-12 | SM00058 | | S | | SM00062 | | | S | 150-199, 275-278 | | |
| 038 | 22 | | PA | 2-0 | 33-24-12 | SM00062 | | S | | D03220 | | 3 | | 050-099 | | |
| 038 | 20 | | PA | 1-11 | 33-24-12 | SM00062 | | S | | D03220 | | 3 | | 150-199 | | |
| 038 | 20 | | PA | 2-5 | 33-24-12 | SM00062 | | S | | D03220 | | 3 | | 275-278 | | |
| 038 | 20 | | PA | 2-1 | 33-24-12 | SM00062 | | S | | D03220 | | 3 | | 280-299 | | |
| 039 | 22 | | PA | 2-0 | 33-24-12 | SM00061 | | S | | D03220 | | 4 | | 050-099 | | |
| 039 | 20 | | PA | 1-11 | 33-24-12 | SM00061 | | S | | D03220 | | 4 | | 150-199 | | |
| 039 | 20 | | PA | 2-5 | 33-24-12 | SM00061 | | S | | D03220 | | 4 | | 275-278 | | |
| 039 | 20 | | PA | 2-1 | 33-24-12 | SM00061 | | S | | D03220 | | 4 | | 280-299 | | |
| 040 | 20 | | PA | 3-11 | 33-24-12 | GD02112 | A.. | E | | D03220 | | 5 | | 050-099 | | |
| 040 | 20 | | PA | 4-1 | 33-24-12 | GD02112 | A.. | E | | D03220 | | 5 | | 150-199 | | |
| 040 | 20 | | PA | 3-7 | 33-24-12 | GD02112 | A.. | E | | D03220 | | 5 | | 275-278 | | |
| 040 | 20 | | PA | 4-0 | 33-24-12 | GD02112 | A.. | E | | D03220 | | 5 | | 280-299 | | |
| 043 | 22 | | PA | 2-9 | 33-24-12 | SM00062 | | S | | D03222 | | 3 | | 050-099 | | |
| 043 | 20 | | PA | 2-9 | 33-24-12 | SM00062 | | S | | D03222 | | 3 | | 150-199, 275-278 | | |
| 043 | 20 | | PA | 3-3 | 33-24-12 | SM00062 | | S | | D03222 | | 3 | | 280-299 | | |
| 044 | 22 | | PA | 2-9 | 33-24-12 | SM00061 | | S | | D03222 | | 4 | | 050-099 | | |
| 044 | 20 | | PA | 2-9 | 33-24-12 | SM00061 | | S | | D03222 | | 4 | | 150-199, 275-278 | | |
| 044 | 20 | | PA | 3-3 | 33-24-12 | SM00061 | | S | | D03222 | | 4 | | 280-299 | | |
| 045 | 20 | | PA | 4-4 | 33-24-12 | GD02118 | A.. | E | | D03222 | | 5 | | 050-099 | | |
| 045 | 20 | | PA | 4-5 | 33-24-12 | GD04996 | A.. | E | | D03222 | | 5 | | 150-199, 275-278 | | |
| 045 | 20 | | PA | 17-3 | 33-24-12 | GD00123 | A.. | E | | D03222 | | 5 | | 280-299 | | |
| 046 | 18 | | PA | 6-3 | 33-24-12 | SM00061 | | S | | SM00065 | | | S | 050-099 | | |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0800 | 286T0800 | | | SPEAKERS AND PASS SIGNS,FWD LEFT (continued) | | | | | | | | | | | |
| 046 | 18 | | PA | | 6-0 | 33-24-12 | SM00061 | | | | SM00147 | | | | 150-199, 275-278 |
| 046 | 18 | | PA | | 5-2 | 33-24-12 | SM00061 | | | | SM00147 | | | | 280-299 |
| 047 | 18 | | PA | | 6-3 | 33-24-12 | SM00062 | | | | SM00066 | | | | 050-099 |
| 047 | 18 | | PA | | 6-0 | 33-24-12 | SM00062 | | | | SM00148 | | | | 150-199, 275-278 |
| 047 | 18 | | PA | | 5-2 | 33-24-12 | SM00062 | | | | SM00148 | | S | | 280-299 |
| 048 | 22 | | PA | | 1-8 | 33-24-12 | SM00066 | | | | D03224 | | 3 | | 050-099 |
| 048 | 20 | | PA | | 1-9 | 33-24-12 | SM00064 | | | | D03224 | | 3 | | 275-278 |
| 048 | 20 | | PA | | 3-1 | 33-24-12 | SM00064 | | | | D03224 | | 3 | | 280-299 |
| 049 | 22 | | PA | | 1-8 | 33-24-12 | SM00065 | | | | D03224 | | 4 | | 050-099 |
| 049 | 20 | | PA | | 1-9 | 33-24-12 | SM00063 | | | | D03224 | | 4 | | 275-278 |
| 049 | 20 | | PA | | 3-1 | 33-24-12 | SM00063 | | | | D03224 | | 4 | | 280-299 |
| 050 | 20 | | PA | | 1-8 | 33-24-12 | GD02118 | | A.. | E | D03224 | | 5 | | 050-099 |
| 050 | 20 | | PA | | 3-2 | 33-24-12 | GD05000 | | A.. | E | D03224 | | 5 | | 275-278 |
| 050 | 20 | | PA | | 4-0 | 33-24-12 | GD05000 | | A.. | E | D03224 | | 5 | | 280-299 |
| 051 | 18 | | PA | | 3-1 | 33-24-12 | SM00069 | | | | D06514J | | 4 | DK | 150-199 |
| 051 | 18 | | PA | | 4-2 | 33-24-12 | SM00063 | | | | D06514J | | 4 | DK | 275-278 |
| 051 | 18 | | PA | | 1-0 | 33-24-12 | SM00063 | | | | D06514J | | 4 | DK | 280-299 |
| 052 | 18 | | PA | | 3-1 | 33-24-12 | SM00070 | | | | D06514J | | 3 | DK | 150-199 |
| 052 | 18 | | PA | | 4-2 | 33-24-12 | SM00064 | | | | D06514J | | 3 | DK | 275-278 |
| 052 | 18 | | PA | | 1-0 | 33-24-12 | SM00064 | | | | D06514J | | 3 | DK | 280-299 |
| 053 | 22 | | PA | | 2-11 | 33-24-12 | SM00066 | | | | D03226 | | 3 | | 050-099 |
| 053 | 20 | | PA | | 2-9 | 33-24-12 | SM00152 | | | | D03226 | | 3 | | 150-199 |
| 054 | 22 | | PA | | 2-11 | 33-24-12 | SM00065 | | | | D03226 | | 4 | | 050-099 |
| 054 | 20 | | PA | | 2-9 | 33-24-12 | SM00151 | | | | D03226 | | 4 | | 150-199 |
| 055 | 20 | | PA | | 3-11 | 33-24-12 | GD02118 | | A.. | E | D03226 | | 5 | | 050-099 |
| 055 | 20 | | PA | | 3-11 | 33-24-12 | GD05652 | | A.. | E | D03226 | | 5 | | 150-199 |
| 056 | 18 | | PA | | 6-4 | 33-24-12 | SM00065 | | | | SM00069 | | | S | 050-099 |
| 056 | 18 | | PA | | 6-11 | 33-24-12 | SM00069 | | | | SM00151 | | | S | 150-199 |
| 057 | 18 | | PA | | 6-4 | 33-24-12 | SM00066 | | | | SM00070 | | | S | 050-099 |
| 057 | 18 | | PA | | 6-11 | 33-24-12 | SM00070 | | | | SM00152 | | | S | 150-199 |
| 058 | 22 | | PA | | 1-9 | 33-24-12 | SM00070 | | | | D03228 | | 3 | | 050-099 |
| 058 | 20 | | PA | | 2-6 | 33-24-12 | SM00070 | | | | D03228 | | 3 | | 150-199 |
| 059 | 22 | | PA | | 1-9 | 33-24-12 | SM00069 | | | | D03228 | | 4 | | 050-099 |
| 059 | 20 | | PA | | 2-6 | 33-24-12 | SM00069 | | | | D03228 | | 4 | | 150-199 |
| 060 | 20 | | PA | | 4-2 | 33-24-12 | GD02124 | | A.. | E | D03228 | | 5 | | 050-099 |
| 060 | 20 | | PA | | 2-9 | 33-24-12 | GD05652 | | A.. | E | D03228 | | 5 | | 150-199 |
| 063 | 22 | | PA | | 3-1 | 33-24-12 | SM00070 | | | | D03230 | | 3 | | 050-099 |
| 064 | 22 | | PA | | 3-1 | 33-24-12 | SM00069 | | | | D03230 | | 4 | | 050-099 |
| 065 | 20 | | PA | | 1-8 | 33-24-12 | GD02124 | | A.. | E | D03230 | | 5 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0800 | 286T0800 | | | SPEAKERS AND PASS SIGNS,FWD LEFT (continued) | | | | | | | | | | | |
| 066 | 18 | | PA | | 4-0 | 33-24-12 | SM00069 | | | | SM00071 | | | S | 050-099 |
| 067 | 18 | | PA | | 4-0 | 33-24-12 | SM00070 | | | | SM00072 | | | S | 050-099 |
| 068 | 22 | | PA | | 3-2 | 33-24-12 | SM00072 | | | | D03232 | 3 | | | 050-099 |
| 069 | 22 | | PA | | 3-2 | 33-24-12 | SM00071 | | | | D03232 | 4 | | | 050-099 |
| 070 | 20 | | PA | | 4-3 | 33-24-12 | GD02124 | A.. | E | | D03232 | 5 | | | 050-099 |
| 071 | 18 | | PA | | 24-6 | 33-24-12 | SM00071 | | | | SM00077 | | | S | 050-099 |
| 072 | 18 | | PA | | 24-6 | 33-24-12 | SM00072 | | | | SM00078 | | | S | 050-099 |
| 083 | 22 | | PA | | 1-10 | 33-24-12 | SM00078 | | | | D03238 | 3 | | | 050-099 |
| 084 | 22 | | PA | | 1-10 | 33-24-12 | SM00077 | | | | D03238 | 4 | | | 050-099 |
| 085 | 20 | | PA | | 3-0 | 33-24-12 | GD02136 | A.. | E | | D03238 | 5 | | | 050-099 |
| 086 | 18 | | PA | | 4-8 | 33-24-12 | SM00077 | | | | SM00081 | | | S | 050-099 |
| 087 | 18 | | PA | | 4-8 | 33-24-12 | SM00078 | | | | SM00082 | | | S | 050-099 |
| 088 | 22 | | PA | | 3-7 | 33-24-12 | SM00082 | | | | D03240 | 3 | | | 050-099 |
| 089 | 22 | | PA | | 3-7 | 33-24-12 | SM00081 | | | | D03240 | 4 | | | 050-099 |
| 090 | 20 | | PA | | 1-8 | 33-24-12 | GD02136 | A.. | E | | D03240 | 5 | | | 050-099 |
| 093 | 22 | | PA | | 1-8 | 33-24-12 | SM00082 | | | | D03242 | 3 | | | 050-099 |
| 094 | 22 | | PA | | 1-8 | 33-24-12 | SM00081 | | | | D03242 | 4 | | | 050-099 |
| 095 | 20 | | PA | | 4-7 | 33-24-12 | GD02136 | A.. | E | | D03242 | 5 | | | 050-099 |
| 096 | 18 | | PA | | 4-11 | 33-24-12 | SM00081 | | | | SM00085 | | | S | 050-099 |
| 097 | 18 | | PA | | 4-11 | 33-24-12 | SM00082 | | | | SM00086 | | | S | 050-099 |
| 098 | 22 | | PA | | 2-11 | 33-24-12 | SM00086 | | | | D03244 | 3 | | | 050-099 |
| 099 | 22 | | PA | | 2-11 | 33-24-12 | SM00085 | | | | D03244 | 4 | | | 050-099 |
| 100 | 20 | | PA | | 4-5 | 33-24-12 | GD02140 | A.. | E | | D03244 | 5 | | | 050-099 |
| 103 | 22 | | PA | | 2-0 | 33-24-12 | SM00086 | | | | D03246 | 3 | | | 050-099 |
| 104 | 22 | | PA | | 2-0 | 33-24-12 | SM00085 | | | | D03246 | 4 | | | 050-099 |
| 105 | 20 | | PA | | 1-9 | 33-24-12 | GD02140 | A.. | E | | D03246 | 5 | | | 050-099 |
| 106 | 18 | | PA | | 2-10 | 33-24-12 | SM00085 | | | | SM00087 | | | S | 050-099 |
| 107 | 18 | | PA | | 2-10 | 33-24-12 | SM00086 | | | | SM00088 | | | S | 050-099 |
| 108 | 22 | | PA | | 3-0 | 33-24-12 | SM00088 | | | | D03248 | 3 | | | 050-099 |
| 109 | 22 | | PA | | 3-0 | 33-24-12 | SM00087 | | | | D03248 | 4 | | | 050-099 |
| 110 | 20 | | PA | | 3-11 | 33-24-12 | GD02140 | A.. | E | | D03248 | 5 | | | 050-099 |
| 111 | 18 | | PA | | 12-6 | 33-24-12 | SM00087 | | | | D05184P | 4 | | | 050-099 |
| 112 | 18 | | PA | | 12-6 | 33-24-12 | SM00088 | | | | D05184P | 7 | | | 050-099 |
| 114 | 18 | | PA | | 8-1 | 33-24-12 | D05182P | | 4 | | SM00045 | | | S | 050-099 |
| 114 | 18 | | PA | | 10-1 | 33-24-12 | D05182P | | 4 | | SM00045 | | | S | 275-278 |
| 114 | 18 | | PA | | 8-9 | 33-24-12 | D05182P | | 4 | | SM00045 | | | S | 280-299 |
| 115 | 18 | | PA | | 8-1 | 33-24-12 | D05182P | | 7 | | SM00046 | | | S | 050-099 |
| 115 | 18 | | PA | | 10-1 | 33-24-12 | D05182P | | 7 | | SM00046 | | | S | 275-278 |
| 115 | 18 | | PA | | 8-9 | 33-24-12 | D05182P | | 7 | | SM00046 | | | S | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0800 | 286T0800 | | | SPEAKERS AND PASS SIGNS,FWD LEFT (continued) | | | | | | | | | | | |
| 116 | 20 | | PA | | 1-9 | 33-24-12 | D03200 | | | | SM00046 | | S | | 275-278 |
| 116 | 20 | | PA | | 2-11 | 33-24-12 | D03200 | | | | SM00046 | | S | | 280-299 |
| 117 | 20 | | PA | | 1-9 | 33-24-12 | D03200 | | | | SM00045 | | S | | 275-278 |
| 117 | 20 | | PA | | 2-11 | 33-24-12 | D03200 | | | | SM00045 | | S | | 280-299 |
| 118 | 20 | | PA | | 4-5 | 33-24-12 | D03200 | | | | GD05156 | A.. | E | | 275-278 |
| 118 | 20 | | PA | | 4-2 | 33-24-12 | D03200 | | | | GD05156 | A.. | E | | 280-299 |
| 201B | 22 | | PB | A | 11-1 | 23-31-15 | D05182P | | | | SM00006 | | S | | 050-099 |
| 201B | 22 | | PB | A | 12-2 | 23-31-15 | D05182P | | | | SM00006 | | S | | 150-199 |
| 201B | 22 | | PB | A | 10-1 | 23-31-15 | D05182P | | | | SM00092 | | S | | 275-278 |
| 201B | 22 | | PB | A | 8-9 | 23-31-15 | D05182P | | | | SM00002 | | S | | 280-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-15 | D05182P | | | | SM00005 | | S | | 050-099, 150-199 |
| 201R | 22 | | PB | A | 0-0 | 23-31-15 | D05182P | | | | SM00091 | | S | | 275-278 |
| 201R | 22 | | PB | A | 0-0 | 23-31-15 | D05182P | | | | SM00001 | | S | | 280-299 |
| 202B | 22 | | PB | B | 10-4 | 23-31-15 | D05182P | | | | D03206 | | 2 | | 050-099 |
| 202B | 22 | | PB | B | 10-6 | 23-31-15 | D05182P | | | | D03206 | | 2 | | 150-199 |
| 202B | 22 | | PB | B | 3-8 | 23-31-15 | SM00092 | | S | | D03206 | | 2 | | 275-278 |
| 202B | 22 | | PB | B | 1-10 | 23-31-15 | SM00002 | | S | | D03206 | | 2 | | 280-299 |
| 202R | 22 | | PB | B | 0-0 | 23-31-15 | D05182P | | 8 | | D03206 | | 1 | | 050-099, 150-199 |
| 202R | 22 | | PB | B | 0-0 | 23-31-15 | SM00091 | | S | | D03206 | | 1 | | 275-278 |
| 202R | 22 | | PB | B | 0-0 | 23-31-15 | SM00001 | | S | | D03206 | | 1 | | 280-299 |
| 203B | 22 | | PB | C | 6-4 | 23-31-15 | SM00092 | | S | | SM00006 | | S | | 275-278 |
| 203B | 22 | | PB | C | 4-8 | 23-31-15 | SM00002 | | S | | SM00006 | | S | | 280-299 |
| 203R | 22 | | PB | C | 0-0 | 23-31-15 | SM00091 | | S | | SM00005 | | S | | 275-278 |
| 203R | 22 | | PB | C | 0-0 | 23-31-15 | SM00001 | | S | | SM00005 | | S | | 280-299 |
| 204B | 22 | | PB | D | 1-8 | 23-31-15 | SM00006 | | S | | D03208 | | 2 | | 050-099 |
| 204B | 22 | | PB | D | 2-1 | 23-31-15 | SM00006 | | S | | D03208 | | 2 | | 150-199, 275-278 |
| 204B | 22 | | PB | D | 2-5 | 23-31-15 | SM00006 | | S | | D03208 | | 2 | | 280-299 |
| 204R | 22 | | PB | D | 0-0 | 23-31-15 | SM00005 | | S | | D03208 | | 1 | | ALL |
| 206B | 22 | | PB | F | 2-7 | 23-31-15 | SM00006 | | S | | D03210 | | 2 | | 050-099 |
| 206B | 22 | | PB | F | 1-8 | 23-31-15 | SM00006 | | S | | D03210 | | 2 | | 150-199, 275-278 |
| 206B | 22 | | PB | F | 2-0 | 23-31-15 | SM00006 | | S | | D03210 | | 2 | | 280-299 |
| 206R | 22 | | PB | F | 0-0 | 23-31-15 | SM00005 | | S | | D03210 | | 1 | | ALL |
| 207B | 22 | | PB | G | 6-10 | 23-31-15 | SM00006 | | S | | SM00010 | | S | | 050-099 |
| 207B | 22 | | PB | G | 5-0 | 23-31-15 | SM00006 | | S | | SM00010 | | S | | 150-199, 275-278 |
| 207B | 22 | | PB | G | 5-3 | 23-31-15 | SM00006 | | S | | SM00010 | | S | | 280-299 |
| 207R | 22 | | PB | G | 0-0 | 23-31-15 | SM00005 | | S | | SM00009 | | S | | ALL |
| 208B | 22 | | PB | H | 3-2 | 23-31-15 | SM00010 | | S | | D03212 | | 2 | | 050-099 |
| 208B | 22 | | PB | H | 1-8 | 23-31-15 | SM00010 | | S | | D03212 | | 2 | | 150-199, 275-278 |
| 208B | 22 | | PB | H | 1-10 | 23-31-15 | SM00010 | | S | | D03212 | | 2 | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0800 | 286T0800 | | | SPEAKERS AND PASS SIGNS,FWD LEFT (continued) | | | | | | | | | | | |
| 208R | 22 | PB | H | 0-0 | 23-31-15 | SM00009 | | | S | D03212 | 1 | | | ALL | |
| 210B | 22 | PB | K | 1-7 | 23-31-15 | SM00010 | | | S | D03214 | 2 | | | 050-099 | |
| 210B | 22 | PB | K | 3-2 | 23-31-15 | SM00010 | | | S | D03214 | 2 | | | 150-199 | |
| 210B | 22 | PB | K | 2-9 | 23-31-15 | SM00010 | | | S | D03214 | 2 | | | 275-278 | |
| 210B | 22 | PB | K | 2-10 | 23-31-15 | SM00010 | | | S | D03214 | 2 | | | 280-299 | |
| 210R | 22 | PB | K | 0-0 | 23-31-15 | SM00009 | | | S | D03214 | 1 | | | ALL | |
| 211B | 22 | PB | L | 6-4 | 23-31-15 | SM00010 | | | S | SM00014 | | S | | 050-099 | |
| 211B | 22 | PB | L | 6-0 | 23-31-15 | SM00010 | | | S | SM00013 | | S | | 150-199, 275-278 | |
| 211B | 22 | PB | L | 7-0 | 23-31-15 | SM00010 | | | S | SM00014 | | S | | 280-299 | |
| 211R | 22 | PB | L | 0-0 | 23-31-15 | SM00009 | | | S | SM00013 | | S | | 050-099, 280-299 | |
| 211R | 22 | PB | L | 0-0 | 23-31-15 | SM00009 | | | S | SM00014 | | S | | 150-199, 275-278 | |
| 212B | 22 | PB | M | 3-1 | 23-31-15 | SM00014 | | | S | D03216 | 2 | | | 050-099 | |
| 212B | 22 | PB | M | 1-11 | 23-31-15 | SM00013 | | | S | D03216 | 2 | | | 150-199 | |
| 212B | 22 | PB | M | 1-10 | 23-31-15 | SM00013 | | | S | D03216 | 2 | | | 275-278 | |
| 212B | 22 | PB | M | 3-3 | 23-31-15 | SM00014 | | | S | D03216 | 2 | | | 280-299 | |
| 212R | 22 | PB | M | 0-0 | 23-31-15 | SM00013 | | | S | D03216 | 1 | | | 050-099, 280-299 | |
| 212R | 22 | PB | M | 0-0 | 23-31-15 | SM00014 | | | S | D03216 | 1 | | | 150-199, 275-278 | |
| 214B | 22 | PB | P | 1-10 | 23-31-15 | SM00014 | | | S | D03218 | 2 | | | 050-099 | |
| 214B | 22 | PB | P | 3-1 | 23-31-15 | SM00013 | | | S | D03218 | 2 | | | 150-199, 275-278 | |
| 214B | 22 | PB | P | 2-1 | 23-31-15 | SM00014 | | | S | D03218 | 2 | | | 280-299 | |
| 214R | 22 | PB | P | 0-0 | 23-31-15 | SM00013 | | | S | D03218 | 1 | | | 050-099, 280-299 | |
| 214R | 22 | PB | P | 0-0 | 23-31-15 | SM00014 | | | S | D03218 | 1 | | | 150-199, 275-278 | |
| 215B | 22 | PB | R | 5-5 | 23-31-15 | SM00014 | | | S | SM00018 | | S | | 050-099, 280-299 | |
| 215B | 22 | PB | R | 6-1 | 23-31-15 | SM00013 | | | S | SM00017 | | S | | 150-199, 275-278 | |
| 215R | 22 | PB | R | 0-0 | 23-31-15 | SM00013 | | | S | SM00017 | | S | | 050-099, 280-299 | |
| 215R | 22 | PB | R | 0-0 | 23-31-15 | SM00014 | | | S | SM00018 | | S | | 150-199, 275-278 | |
| 216B | 22 | PB | T | 2-0 | 23-31-15 | SM00018 | | | S | D03220 | 2 | | | 050-099 | |
| 216B | 22 | PB | T | 1-11 | 23-31-15 | SM00017 | | | S | D03220 | 2 | | | 150-199 | |
| 216B | 22 | PB | T | 2-5 | 23-31-15 | SM00017 | | | S | D03220 | 2 | | | 275-278 | |
| 216B | 22 | PB | T | 2-1 | 23-31-15 | SM00018 | | | S | D03220 | 2 | | | 280-299 | |
| 216R | 22 | PB | T | 0-0 | 23-31-15 | SM00017 | | | S | D03220 | 1 | | | 050-099, 280-299 | |
| 216R | 22 | PB | T | 0-0 | 23-31-15 | SM00018 | | | S | D03220 | 1 | | | 150-199, 275-278 | |
| 218B | 22 | PB | V | 2-9 | 23-31-15 | SM00018 | | | S | D03222 | 2 | | | 050-099 | |
| 218B | 22 | PB | V | 2-9 | 23-31-15 | SM00017 | | | S | D03222 | 2 | | | 150-199, 275-278 | |
| 218B | 22 | PB | V | 3-3 | 23-31-15 | SM00018 | | | S | D03222 | 2 | | | 280-299 | |
| 218R | 22 | PB | V | 0-0 | 23-31-15 | SM00017 | | | S | D03222 | 1 | | | 050-099, 280-299 | |
| 218R | 22 | PB | V | 0-0 | 23-31-15 | SM00018 | | | S | D03222 | 1 | | | 150-199, 275-278 | |
| 219B | 22 | PB | W | 6-3 | 23-31-15 | SM00018 | | | S | SM00022 | | S | | 050-099 | |
| 219B | 22 | PB | W | 6-0 | 23-31-15 | SM00017 | | | S | SM00164 | | S | | 150-199, 275-278 | |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0800 | 286T0800 | | | SPEAKERS AND PASS SIGNS,FWD LEFT (continued) | | | | | | | | | | | |
| 219B | 22 | PB | W | | 5-2 | 23-31-15 | SM00018 | | S | | SM00022 | | S | | 280-299 |
| 219R | 22 | PB | W | | 0-0 | 23-31-15 | SM00017 | | S | | SM00021 | | S | | 050-099, 280-299 |
| 219R | 22 | PB | W | | 0-0 | 23-31-15 | SM00018 | | S | | SM00165 | | S | | 150-199, 275-278 |
| 220B | 22 | PB | X | | 1-8 | 23-31-15 | SM00022 | | S | | D03224 | 2 | | | 050-099 |
| 220B | 22 | PB | X | | 1-9 | 23-31-15 | SM00019 | | S | | D03224 | 2 | | | 275-278 |
| 220B | 22 | PB | X | | 2-2 | 23-31-15 | SM00022 | | S | | D08138 | 2 | | | 280-299 |
| 220R | 22 | PB | X | | 0-0 | 23-31-15 | SM00021 | | S | | D03224 | 1 | | | 050-099 |
| 220R | 22 | PB | X | | 0-0 | 23-31-15 | SM00020 | | S | | D03224 | 1 | | | 275-278 |
| 220R | 22 | PB | X | | 0-0 | 23-31-15 | SM00021 | | S | | D08138 | 1 | | | 280-299 |
| 221B | 22 | PB | Y | | 2-1 | 23-31-15 | SM00019 | | S | | D06514J | 2 | | | 150-199 |
| 221B | 22 | PB | Y | | 3-2 | 23-31-15 | SM00019 | | S | | D06514J | 2 | | | 275-278 |
| 221R | 22 | PB | Y | | 0-0 | 23-31-15 | SM00020 | | S | | D06514J | 1 | | | 150-199, 275-278 |
| 222B | 22 | PB | AA | | 2-11 | 23-31-15 | SM00022 | | S | | D03226 | 2 | | | 050-099 |
| 222B | 22 | PB | BM | | 2-9 | 23-31-15 | SM00168 | | S | | D03226 | 2 | | | 150-199 |
| 222B | 22 | PB | IV | | 3-11 | 23-31-15 | D08140 | 2 | | | SM00022 | | S | | 280-299 |
| 222R | 22 | PB | AA | | 0-0 | 23-31-15 | SM00021 | | S | | D03226 | 1 | | | 050-099 |
| 222R | 22 | PB | BM | | 0-0 | 23-31-15 | SM00169 | | S | | D03226 | 1 | | | 150-199 |
| 222R | 22 | PB | IV | | 0-0 | 23-31-15 | D08140 | 1 | | | SM00021 | | S | | 280-299 |
| 223B | 22 | PB | AB | | 6-4 | 23-31-15 | SM00022 | | S | | SM00026 | | S | | 050-099 |
| 223B | 22 | PB | IW | | 22-4 | 23-31-15 | SM00022 | | S | | SM00026 | | S | | 280-299 |
| 223R | 22 | PB | AB | | 0-0 | 23-31-15 | SM00021 | | S | | SM00025 | | S | | 050-099 |
| 223R | 22 | PB | IW | | 0-0 | 23-31-15 | SM00021 | | S | | SM00025 | | S | | 280-299 |
| 224B | 22 | PB | AC | | 1-9 | 23-31-15 | SM00026 | | S | | D03228 | 2 | | | 050-099 |
| 224B | 22 | PB | X | | 2-6 | 23-31-15 | SM00019 | | S | | D03228 | 2 | | | 150-199 |
| 224B | 22 | PB | IX | | 1-8 | 23-31-15 | D08142 | 2 | | | SM00026 | | S | | 280-299 |
| 224R | 22 | PB | AC | | 0-0 | 23-31-15 | SM00025 | | S | | D03228 | 1 | | | 050-099 |
| 224R | 22 | PB | X | | 0-0 | 23-31-15 | SM00020 | | S | | D03228 | 1 | | | 150-199 |
| 224R | 22 | PB | IX | | 0-0 | 23-31-15 | D08142 | 1 | | | SM00025 | | S | | 280-299 |
| 226B | 22 | PB | AE | | 3-1 | 23-31-15 | SM00026 | | S | | D03230 | 2 | | | 050-099 |
| 226B | 22 | PB | JA | | 3-3 | 23-31-15 | D08144 | 2 | | | SM00026 | | S | | 280-299 |
| 226R | 22 | PB | AE | | 0-0 | 23-31-15 | SM00025 | | S | | D03230 | 1 | | | 050-099 |
| 226R | 22 | PB | JA | | 0-0 | 23-31-15 | D08144 | 1 | | | SM00025 | | S | | 280-299 |
| 227B | 22 | PB | JB | | 7-1 | 23-31-15 | SM00026 | | S | | SM00030 | | S | | 280-299 |
| 227R | 22 | PB | JB | | 0-0 | 23-31-15 | SM00025 | | S | | SM00029 | | S | | 280-299 |
| 228B | 22 | PB | AG | | 6-2 | 23-31-15 | SM00026 | | S | | D03232 | 2 | | | 050-099 |
| 228B | 22 | PB | JC | | 3-1 | 23-31-15 | D03224 | 2 | | | SM00030 | | S | | 280-299 |
| 228R | 22 | PB | AG | | 0-0 | 23-31-15 | SM00025 | | S | | D03232 | 1 | | | 050-099 |
| 228R | 22 | PB | JC | | 0-0 | 23-31-15 | D03224 | 1 | | | SM00029 | | S | | 280-299 |
| 231B | 22 | PB | JF | | 1-0 | 23-31-15 | D06514J | 2 | | | SM00030 | | S | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0800 | 286T0800 | | | SPEAKERS AND PASS SIGNS,FWD LEFT (continued) | | | | | | | | | | | | | | |
| 231R | 22 | PB | JF | | 0-0 | 23-31-15 | D06514J | | 1 | | | | | SM00029 | | S | | 280-299 |
| 234B | 22 | PB | AN | | 3-0 | 23-31-15 | SM00036 | | | S | | | | D03238 | 2 | | | 050-099 |
| 234R | 22 | PB | AN | | 0-0 | 23-31-15 | SM00035 | | | S | | | | D03238 | 1 | | | 050-099 |
| 236B | 22 | PB | AR | | 1-7 | 23-31-15 | SM00036 | | | S | | | | D03240 | 2 | | | 050-099 |
| 236R | 22 | PB | AR | | 0-0 | 23-31-15 | SM00035 | | | S | | | | D03240 | 1 | | | 050-099 |
| 237B | 22 | PB | AT | | 4-6 | 23-31-15 | SM00036 | | | S | | | | SM00040 | | S | | 050-099 |
| 237R | 22 | PB | AT | | 0-0 | 23-31-15 | SM00035 | | | S | | | | SM00039 | | S | | 050-099 |
| 238B | 22 | PB | AU | | 2-1 | 23-31-15 | SM00040 | | | S | | | | D03242 | 2 | | | 050-099 |
| 238R | 22 | PB | AU | | 0-0 | 23-31-15 | SM00039 | | | S | | | | D03242 | 1 | | | 050-099 |
| 240B | 22 | PB | AW | | 1-8 | 23-31-15 | SM00040 | | | S | | | | D03244 | 2 | | | 050-099 |
| 240R | 22 | PB | AW | | 0-0 | 23-31-15 | SM00039 | | | S | | | | D03244 | 1 | | | 050-099 |
| 241B | 22 | PB | AX | | 5-2 | 23-31-15 | SM00040 | | | S | | | | SM00044 | | S | | 050-099 |
| 241R | 22 | PB | AX | | 0-0 | 23-31-15 | SM00039 | | | S | | | | SM00043 | | S | | 050-099 |
| 242B | 22 | PB | AY | | 1-7 | 23-31-15 | SM00044 | | | S | | | | D03246 | 2 | | | 050-099 |
| 242R | 22 | PB | AY | | 0-0 | 23-31-15 | SM00043 | | | S | | | | D03246 | 1 | | | 050-099 |
| 244B | 22 | PB | BB | | 3-0 | 23-31-15 | SM00044 | | | S | | | | D03248 | 2 | | | 050-099 |
| 244R | 22 | PB | BB | | 0-0 | 23-31-15 | SM00043 | | | S | | | | D03248 | 1 | | | 050-099 |
| 245B | 22 | PB | BC | | 12-6 | 23-31-15 | SM00044 | | | S | | | | D05184P | 2 | | | 050-099 |
| 245R | 22 | PB | BC | | 0-0 | 23-31-15 | SM00043 | | | S | | | | D05184P | 1 | | | 050-099 |
| 246B | 22 | PB | BD | | 1-9 | 23-31-15 | D03200 | | | | 2 | | | SM00092 | | S | | 275-278 |
| 246B | 22 | PB | BD | | 2-11 | 23-31-15 | D03200 | | | | 2 | | | SM00002 | | S | | 280-299 |
| 246R | 22 | PB | BD | | 0-0 | 23-31-15 | D03200 | | | | 1 | | | SM00091 | | S | | 275-278 |
| 246R | 22 | PB | BD | | 0-0 | 23-31-15 | D03200 | | | | 1 | | | SM00001 | | S | | 280-299 |
| 248B | 22 | PB | BF | | 2-1 | 23-31-15 | SM00164 | | | S | | | | D08138 | 2 | | | 150-199, 275-278 |
| 248R | 22 | PB | BF | | 0-0 | 23-31-15 | SM00165 | | | S | | | | D08138 | 1 | | | 150-199, 275-278 |
| 251B | 22 | PB | CB | | 11-1 | 23-31-15 | D05182P | | | | 5 | | | SM00106 | | S | | 050-099 |
| 251B | 22 | PB | BA | | 12-2 | 23-31-15 | D05182P | | | | 5 | | | SM00106 | | S | | 150-199 |
| 251R | 22 | PB | CB | | 0-0 | 23-31-15 | D05182P | | | | 6 | | | SM00105 | | S | | 050-099 |
| 251R | 22 | PB | BA | | 0-0 | 23-31-15 | D05182P | | | | 6 | | | SM00105 | | S | | 150-199 |
| 254B | 22 | PB | DV | | 1-8 | 23-31-15 | SM00106 | | | S | | | | D03208 | 7 | | | 050-099 |
| 254B | 22 | PB | BE | | 2-1 | 23-31-15 | D03208 | | | | 7 | | | SM00106 | | S | | 150-199 |
| 254R | 22 | PB | DV | | 0-0 | 23-31-15 | SM00105 | | | S | | | | D03208 | 6 | | | 050-099 |
| 254R | 22 | PB | BE | | 0-0 | 23-31-15 | D03208 | | | | 6 | | | SM00105 | | S | | 150-199 |
| 256B | 22 | PB | DF | | 2-7 | 23-31-15 | SM00106 | | | S | | | | D03210 | 7 | | | 050-099 |
| 256B | 22 | PB | BG | | 1-8 | 23-31-15 | D03210 | | | | 7 | | | SM00106 | | S | | 150-199 |
| 256R | 22 | PB | DF | | 0-0 | 23-31-15 | SM00105 | | | S | | | | D03210 | 6 | | | 050-099 |
| 256R | 22 | PB | BG | | 0-0 | 23-31-15 | D03210 | | | | 6 | | | SM00105 | | S | | 150-199 |
| 257B | 22 | PB | DG | | 6-10 | 23-31-15 | SM00106 | | | S | | | | SM00110 | | S | | 050-099 |
| 257B | 22 | PB | BZ | | 5-0 | 23-31-15 | SM00106 | | | S | | | | SM00110 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0800 | 286T0800 | | | SPEAKERS AND PASS SIGNS,FWD LEFT (continued) | | | | | | | | | | | |
| 257R | 22 | PB | DG | 0-0 | 23-31-15 | SM00105 | | | S | SM00109 | | | S | 050-099 | |
| 257R | 22 | PB | BZ | 0-0 | 23-31-15 | SM00105 | | | S | SM00109 | | | S | 150-199 | |
| 258B | 22 | PB | DH | 3-2 | 23-31-15 | SM00110 | | | S | D03212 | 7 | | | 050-099 | |
| 258B | 22 | PB | CA | 1-8 | 23-31-15 | D03212 | | 7 | | SM00110 | | | S | 150-199 | |
| 258R | 22 | PB | DH | 0-0 | 23-31-15 | SM00109 | | | S | D03212 | 6 | | | 050-099 | |
| 258R | 22 | PB | CA | 0-0 | 23-31-15 | D03212 | | 6 | | SM00109 | | | S | 150-199 | |
| 260B | 22 | PB | DJ | 1-7 | 23-31-15 | SM00110 | | | S | D03214 | 7 | | | 050-099 | |
| 260B | 22 | PB | BJ | 3-2 | 23-31-15 | D03214 | | 7 | | SM00110 | | | S | 150-199 | |
| 260R | 22 | PB | DJ | 0-0 | 23-31-15 | SM00109 | | | S | D03214 | 6 | | | 050-099 | |
| 260R | 22 | PB | BJ | 0-0 | 23-31-15 | D03214 | | 6 | | SM00109 | | | S | 150-199 | |
| 261B | 22 | PB | DK | 6-4 | 23-31-15 | SM00110 | | | S | SM00114 | | | S | 050-099 | |
| 261B | 22 | PB | CB | 6-0 | 23-31-15 | SM00110 | | | S | SM00113 | | | S | 150-199 | |
| 261R | 22 | PB | DK | 0-0 | 23-31-15 | SM00109 | | | S | SM00113 | | | S | 050-099 | |
| 261R | 22 | PB | CB | 0-0 | 23-31-15 | SM00109 | | | S | SM00114 | | | S | 150-199 | |
| 262B | 22 | PB | DL | 3-1 | 23-31-15 | SM00114 | | | S | D03216 | 7 | | | 050-099 | |
| 262B | 22 | PB | CC | 1-11 | 23-31-15 | D03216 | | 7 | | SM00113 | | | S | 150-199 | |
| 262R | 22 | PB | DL | 0-0 | 23-31-15 | SM00113 | | | S | D03216 | 6 | | | 050-099 | |
| 262R | 22 | PB | CC | 0-0 | 23-31-15 | D03216 | | 6 | | SM00114 | | | S | 150-199 | |
| 264B | 22 | PB | DN | 1-10 | 23-31-15 | SM00114 | | | S | D03218 | 7 | | | 050-099 | |
| 264B | 22 | PB | CD | 3-1 | 23-31-15 | D03218 | | 7 | | SM00113 | | | S | 150-199 | |
| 264R | 22 | PB | DN | 0-0 | 23-31-15 | SM00113 | | | S | D03218 | 6 | | | 050-099 | |
| 264R | 22 | PB | CD | 0-0 | 23-31-15 | D03218 | | 6 | | SM00114 | | | S | 150-199 | |
| 265B | 22 | PB | DO | 5-5 | 23-31-15 | SM00114 | | | S | SM00118 | | | S | 050-099 | |
| 265B | 22 | PB | CE | 6-1 | 23-31-15 | SM00113 | | | S | SM00117 | | | S | 150-199 | |
| 265R | 22 | PB | DO | 0-0 | 23-31-15 | SM00113 | | | S | SM00117 | | | S | 050-099 | |
| 265R | 22 | PB | CE | 0-0 | 23-31-15 | SM00114 | | | S | SM00118 | | | S | 150-199 | |
| 266B | 22 | PB | DP | 2-0 | 23-31-15 | SM00118 | | | S | D03220 | 7 | | | 050-099 | |
| 266B | 22 | PB | BN | 1-11 | 23-31-15 | D03220 | | 7 | | SM00117 | | | S | 150-199 | |
| 266R | 22 | PB | DP | 0-0 | 23-31-15 | SM00117 | | | S | D03220 | 6 | | | 050-099 | |
| 266R | 22 | PB | BN | 0-0 | 23-31-15 | D03220 | | 6 | | SM00118 | | | S | 150-199 | |
| 268B | 22 | PB | DR | 2-9 | 23-31-15 | SM00118 | | | S | D03222 | 7 | | | 050-099 | |
| 268B | 22 | PB | BO | 2-9 | 23-31-15 | D03222 | | 7 | | SM00117 | | | S | 150-199 | |
| 268R | 22 | PB | DR | 0-0 | 23-31-15 | SM00117 | | | S | D03222 | 6 | | | 050-099 | |
| 268R | 22 | PB | BO | 0-0 | 23-31-15 | D03222 | | 6 | | SM00118 | | | S | 150-199 | |
| 269B | 22 | PB | DU | 6-3 | 23-31-15 | SM00118 | | | S | SM00122 | | | S | 050-099 | |
| 269B | 22 | PB | BX | 2-1 | 23-31-15 | SM00119 | | | S | D06514J | 6 | | | 150-199 | |
| 269R | 22 | PB | DU | 0-0 | 23-31-15 | SM00121 | | | S | SM00117 | | | S | 050-099 | |
| 269R | 22 | PB | BX | 0-0 | 23-31-15 | SM00120 | | | S | D06514J | 5 | | | 150-199 | |
| 270B | 22 | PB | CC | 1-8 | 23-31-15 | SM00122 | | | S | D03224 | 7 | | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0800 | 286T0800 | | | SPEAKERS AND PASS SIGNS,FWD LEFT (continued) | | | | | | | | | | | | |
| 270R | 22 | PB | CC | | 0-0 | 23-31-15 | SM00121 | | | S | | D03224 | 6 | | | 050-099 |
| 272B | 22 | PB | CE | | 2-11 | 23-31-15 | SM00122 | | | S | | D03226 | 7 | | | 050-099 |
| 272R | 22 | PB | CE | | 0-0 | 23-31-15 | SM00121 | | | S | | D03226 | 6 | | | 050-099 |
| 273B | 22 | PB | CF | | 6-4 | 23-31-15 | SM00122 | | | S | | SM00126 | | S | | 050-099 |
| 273R | 22 | PB | CF | | 0-0 | 23-31-15 | SM00121 | | | S | | SM00125 | | S | | 050-099 |
| 274B | 22 | PB | CG | | 1-9 | 23-31-15 | SM00126 | | | S | | D03228 | 7 | | | 050-099 |
| 274B | 22 | PB | BW | | 2-6 | 23-31-15 | D03228 | | 7 | | | SM00119 | | S | | 150-199 |
| 274R | 22 | PB | CG | | 0-0 | 23-31-15 | SM00125 | | | S | | D03228 | 6 | | | 050-099 |
| 274R | 22 | PB | BW | | 0-0 | 23-31-15 | D03228 | | 6 | | | SM00120 | | S | | 150-199 |
| 276B | 22 | PB | CI | | 3-1 | 23-31-15 | SM00126 | | | S | | D03230 | 7 | | | 050-099 |
| 276R | 22 | PB | CI | | 0-0 | 23-31-15 | SM00125 | | | S | | D03230 | 6 | | | 050-099 |
| 277B | 22 | PB | CJ | | 4-0 | 23-31-15 | SM00126 | | | S | | SM00130 | | S | | 050-099 |
| 277R | 22 | PB | CJ | | 0-0 | 23-31-15 | SM00125 | | | S | | SM00129 | | S | | 050-099 |
| 278B | 22 | PB | CK | | 3-2 | 23-31-15 | SM00130 | | | S | | D03232 | 7 | | | 050-099 |
| 278R | 22 | PB | CK | | 0-0 | 23-31-15 | SM00129 | | | S | | D03232 | 6 | | | 050-099 |
| 279B | 22 | PB | CL | | 23-4 | 23-31-15 | SM00130 | | | S | | SM00136 | | S | | 050-099 |
| 279R | 22 | PB | CL | | 0-0 | 23-31-15 | SM00129 | | | S | | SM00135 | | S | | 050-099 |
| 284B | 22 | PB | CQ | | 3-0 | 23-31-15 | SM00136 | | | S | | D03238 | 7 | | | 050-099 |
| 284R | 22 | PB | CQ | | 0-0 | 23-31-15 | SM00135 | | | S | | D03238 | 6 | | | 050-099 |
| 286B | 22 | PB | CS | | 1-7 | 23-31-15 | SM00136 | | | S | | D03240 | 7 | | | 050-099 |
| 286R | 22 | PB | CS | | 0-0 | 23-31-15 | SM00135 | | | S | | D03240 | 6 | | | 050-099 |
| 287B | 22 | PB | CT | | 4-6 | 23-31-15 | SM00136 | | | S | | SM00140 | | S | | 050-099 |
| 287R | 22 | PB | CT | | 0-0 | 23-31-15 | SM00135 | | | S | | SM00139 | | S | | 050-099 |
| 288B | 22 | PB | CU | | 2-1 | 23-31-15 | SM00140 | | | S | | D03242 | 7 | | | 050-099 |
| 288R | 22 | PB | CU | | 0-0 | 23-31-15 | SM00139 | | | S | | D03242 | 6 | | | 050-099 |
| 290B | 22 | PB | CW | | 1-8 | 23-31-15 | SM00140 | | | S | | D03244 | 7 | | | 050-099 |
| 290R | 22 | PB | CW | | 0-0 | 23-31-15 | SM00139 | | | S | | D03244 | 6 | | | 050-099 |
| 291B | 22 | PB | CY | | 5-2 | 23-31-15 | SM00139 | | | S | | SM00143 | | S | | 050-099 |
| 291R | 22 | PB | CY | | 0-0 | 23-31-15 | SM00140 | | | S | | SM00144 | | S | | 050-099 |
| 292B | 22 | PB | CZ | | 1-7 | 23-31-15 | SM00144 | | | S | | D03246 | 7 | | | 050-099 |
| 292R | 22 | PB | CZ | | 0-0 | 23-31-15 | SM00143 | | | S | | D03246 | 6 | | | 050-099 |
| 294B | 22 | PB | DB | | 3-0 | 23-31-15 | D03248 | | 7 | | | SM00144 | | S | | 050-099 |
| 294R | 22 | PB | DB | | 0-0 | 23-31-15 | D03248 | | 6 | | | SM00143 | | S | | 050-099 |
| 295B | 22 | PB | DC | | 12-6 | 23-31-15 | SM00144 | | | S | | D05184P | 5 | | | 050-099 |
| 295R | 22 | PB | DC | | 0-0 | 23-31-15 | SM00143 | | | S | | D05184P | 6 | | | 050-099 |
| 296B | 22 | PB | BP | | 6-0 | 23-31-15 | SM00117 | | | S | | SM00264 | | S | | 150-199 |
| 296R | 22 | PB | BP | | 0-0 | 23-31-15 | SM00118 | | | S | | SM00265 | | S | | 150-199 |
| 298B | 22 | PB | BH | | 2-10 | 23-31-15 | SM00164 | | | S | | D08140 | 2 | | | 150-199 |
| 298B | 22 | PB | BH | | 2-6 | 23-31-15 | SM00164 | | | S | | D08140 | 2 | | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0800 | 286T0800 | | | SPEAKERS AND PASS SIGNS,FWD LEFT (continued) | | | | | | | | | | | |
| 298R | 22 | PB | BH | | 0-0 | 23-31-15 | SM00165 | | S | | D08140 | | 1 | | 150-199, 275-278 |
| 299B | 22 | PB | BI | | 20-0 | 23-31-15 | SM00164 | | S | | SM00168 | | | S | 150-199 |
| 299B | 22 | PB | BI | | 5-9 | 23-31-15 | SM00164 | | S | | SM00168 | | | S | 275-278 |
| 299R | 22 | PB | BI | | 0-0 | 23-31-15 | SM00165 | | S | | SM00169 | | | S | 150-199, 275-278 |
| 502B | 22 | PB | BK | | 15-6 | 23-31-15 | SM00168 | | S | | D08142 | | 2 | | 150-199 |
| 502B | 22 | PB | BK | | 1-7 | 23-31-15 | SM00168 | | S | | D08142 | | 2 | | 275-278 |
| 502R | 22 | PB | BK | | 0-0 | 23-31-15 | SM00169 | | S | | D08142 | | 1 | | 150-199, 275-278 |
| 503B | 22 | PB | BL | | 6-11 | 23-31-15 | SM00168 | | S | | SM00019 | | | S | 150-199 |
| 503B | 22 | PB | BL | | 5-0 | 23-31-15 | SM00168 | | S | | SM00019 | | | S | 275-278 |
| 503R | 22 | PB | BL | | 0-0 | 23-31-15 | SM00169 | | S | | SM00020 | | | S | 150-199, 275-278 |
| 504B | 22 | PB | BM | | 3-0 | 23-31-15 | SM00168 | | S | | D08144 | | 2 | | 275-278 |
| 504R | 22 | PB | BM | | 0-0 | 23-31-15 | SM00169 | | S | | D08144 | | 1 | | 275-278 |
| 537 | 18 | PA | | | 20-0 | 33-24-12 | SM00147 | | S | | SM00151 | | | S | 150-199 |
| 537 | 18 | PA | | | 5-9 | 33-24-12 | SM00147 | | S | | SM00151 | | | S | 275-278 |
| 537 | 18 | PA | | | 22-4 | 33-24-12 | SM00147 | | S | | SM00151 | | | S | 280-299 |
| 538 | 18 | PA | | | 20-0 | 33-24-12 | SM00148 | | S | | SM00152 | | | S | 150-199 |
| 538 | 18 | PA | | | 5-9 | 33-24-12 | SM00148 | | S | | SM00152 | | | S | 275-278 |
| 538 | 18 | PA | | | 22-4 | 33-24-12 | SM00148 | | S | | SM00152 | | | S | 280-299 |
| 541 | 18 | PA | | | 5-0 | 33-24-12 | SM00151 | | S | | SM00063 | | | S | 275-278 |
| 541 | 18 | PA | | | 7-1 | 33-24-12 | SM00151 | | S | | SM00063 | | | S | 280-299 |
| 542 | 18 | PA | | | 5-0 | 33-24-12 | SM00152 | | S | | SM00064 | | | S | 275-278 |
| 542 | 18 | PA | | | 7-1 | 33-24-12 | SM00152 | | S | | SM00064 | | | S | 280-299 |
| 543 | 20 | PA | | | 2-1 | 33-24-12 | SM00147 | | S | | D08138 | | 4 | | 150-199, 275-278 |
| 543 | 20 | PA | | | 2-2 | 33-24-12 | SM00147 | | S | | D08138 | | 4 | | 280-299 |
| 544 | 20 | PA | | | 2-1 | 33-24-12 | SM00148 | | S | | D08138 | | 3 | | 150-199, 275-278 |
| 544 | 20 | PA | | | 2-2 | 33-24-12 | SM00148 | | S | | D08138 | | 3 | | 280-299 |
| 545 | 20 | PA | | | 1-11 | 33-24-12 | GD04996 | A.. | E | | D08138 | | 5 | | 150-199, 275-278 |
| 545 | 20 | PA | | | 19-10 | 33-24-12 | GD00123 | A.. | E | | D08138 | | 5 | | 280-299 |
| 546 | 20 | PA | | | 2-10 | 33-24-12 | SM00147 | | S | | D08140 | | 4 | | 150-199 |
| 546 | 20 | PA | | | 2-6 | 33-24-12 | SM00147 | | S | | D08140 | | 4 | | 275-278 |
| 546 | 20 | PA | | | 3-11 | 33-24-12 | SM00147 | | S | | D08140 | | 4 | | 280-299 |
| 547 | 20 | PA | | | 2-10 | 33-24-12 | SM00148 | | S | | D08140 | | 3 | | 150-199 |
| 547 | 20 | PA | | | 2-6 | 33-24-12 | SM00148 | | S | | D08140 | | 3 | | 275-278 |
| 547 | 20 | PA | | | 3-11 | 33-24-12 | SM00148 | | S | | D08140 | | 3 | | 280-299 |
| 548 | 20 | PA | | | 4-0 | 33-24-12 | GD04996 | A.. | E | | D08140 | | 5 | | 150-199 |
| 548 | 20 | PA | | | 3-7 | 33-24-12 | GD04996 | A.. | E | | D08140 | | 5 | | 275-278 |
| 548 | 20 | PA | | | 21-7 | 33-24-12 | GD00123 | A.. | E | | D08140 | | 5 | | 280-299 |
| 549 | 20 | PA | | | 15-6 | 33-24-12 | SM00151 | | S | | D08142 | | 4 | | 150-199 |
| 549 | 20 | PA | | | 1-7 | 33-24-12 | SM00151 | | S | | D08142 | | 4 | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|---|-------|------|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0800 | 286T0800 | SPEAKERS AND PASS SIGNS,FWD LEFT (continued) | | | | | | | | | | | | | | |
| 549 | 20 | PA | | 1-8 | 33-24-12 | SM00151 | | S | | D08142 | 4 | | | 280-299 | | |
| 550 | 20 | PA | | 15-6 | 33-24-12 | SM00152 | | S | | D08142 | 3 | | | 150-199 | | |
| 550 | 20 | PA | | 1-7 | 33-24-12 | SM00152 | | S | | D08142 | 3 | | | 275-278 | | |
| 550 | 20 | PA | | 1-8 | 33-24-12 | SM00152 | | S | | D08142 | 3 | | | 280-299 | | |
| 551 | 20 | PA | | 2-2 | 33-24-12 | GD05650 | A.. | E | | D08142 | 5 | | | 150-199 | | |
| 551 | 20 | PA | | 4-5 | 33-24-12 | GD05000 | A.. | E | | D08142 | 5 | | | 275-278 | | |
| 551 | 20 | PA | | 4-4 | 33-24-12 | GD05000 | A.. | E | | D08142 | 5 | | | 280-299 | | |
| 552 | 20 | PA | | 3-0 | 33-24-12 | SM00151 | | S | | D08144 | 4 | | | 275-278 | | |
| 552 | 20 | PA | | 3-3 | 33-24-12 | SM00151 | | S | | D08144 | 4 | | | 280-299 | | |
| 553 | 20 | PA | | 3-0 | 33-24-12 | SM00152 | | S | | D08144 | 3 | | | 275-278 | | |
| 553 | 20 | PA | | 3-3 | 33-24-12 | SM00152 | | S | | D08144 | 3 | | | 280-299 | | |
| 554 | 20 | PA | | 2-3 | 33-24-12 | GD05000 | A.. | E | | D08144 | 5 | | | 275-278 | | |
| 554 | 20 | PA | | 1-10 | 33-24-12 | GD05000 | A.. | E | | D08144 | 5 | | | 280-299 | | |
| 577B | 22 | PB | BQ | 2-1 | 23-31-15 | D08138 | | 7 | | SM00264 | | S | | 150-199 | | |
| 577R | 22 | PB | BQ | 0-0 | 23-31-15 | D08138 | | 6 | | SM00265 | | S | | 150-199 | | |
| 578B | 22 | PB | BR | 2-10 | 23-31-15 | D08140 | | 7 | | SM00264 | | S | | 150-199 | | |
| 578R | 22 | PB | BR | 0-0 | 23-31-15 | D08140 | | 6 | | SM00265 | | S | | 150-199 | | |
| 579B | 22 | PB | BS | 20-0 | 23-31-15 | SM00264 | | S | | SM00268 | | S | | 150-199 | | |
| 579R | 22 | PB | BS | 0-0 | 23-31-15 | SM00265 | | S | | SM00269 | | S | | 150-199 | | |
| 580B | 22 | PB | BT | 15-6 | 23-31-15 | D08142 | | 7 | | SM00268 | | S | | 150-199 | | |
| 580R | 22 | PB | BT | 0-0 | 23-31-15 | D08142 | | 6 | | SM00269 | | S | | 150-199 | | |
| 582B | 22 | PB | BV | 6-11 | 23-31-15 | SM00268 | | S | | SM00119 | | S | | 150-199 | | |
| 582R | 22 | PB | BV | 0-0 | 23-31-15 | SM00269 | | S | | SM00120 | | S | | 150-199 | | |
| 652B | 22 | PB | BU | 2-9 | 23-31-15 | D03226 | | 7 | | SM00268 | | S | | 150-199 | | |
| 652R | 22 | PB | BU | 0-0 | 23-31-15 | D03226 | | 6 | | SM00269 | | S | | 150-199 | | |
| W0802 | 286T0802 | SPEAKERS AND PASS. SIGNS MID CENTER | | | | | | | | | | | | | | |
| 001 | 18 | PA | | 10-0 | 33-24-13 | D05162P | | 4 | | D05968P | 1 | DL | | ALL | | |
| 002 | 18 | PA | | 10-0 | 33-24-13 | D05162P | | 7 | | D05968P | 2 | DL | | ALL | | |
| 201B | 22 | PB | A | 10-0 | 23-31-16 | D05162P | | 2 | | D05968P | 3 | | | ALL | | |
| 201R | 22 | PB | A | 0-0 | 23-31-16 | D05162P | | 1 | | D05968P | 4 | | | ALL | | |
| 202B | 22 | PB | IB | 10-0 | 23-31-16 | D05162P | | 5 | | D05968P | 5 | | | 050-099 | | |
| 202B | 22 | PB | B | 10-0 | 23-31-16 | D05162P | | 5 | | D05968P | 5 | | | 150-199 | | |
| 202R | 22 | PB | IB | 0-0 | 23-31-16 | D05162P | | 6 | | D05968P | 6 | | | 050-099 | | |
| 202R | 22 | PB | B | 0-0 | 23-31-16 | D05162P | | 6 | | D05968P | 6 | | | 150-199 | | |
| W0803 | 286T0803 | WEATHER RADAR R | | | | | | | | | | | | | | |
| 001 | 20 | PA | | 30-0 | 34-43-22 | D00393C | | 2 | | SP00007 | 9 | | | ALL | | |
| 002 | 20 | PA | | 3-0 | 34-43-22 | D00393C | | 7 | | GD00565 | A.. | 2 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0803 | 286T0803 | | | WEATHER RADAR R (continued) | | | | | | | | | | | |
| 003 | 20 | | PA | | 3-0 | 34-43-22 | D00393C | | | | GD00565 | D.. | 2 | | ALL |
| 004 | 20 | | PA | | 9-0 | 34-43-22 | D00393C | | | | D04919J | | 24 | | ALL |
| 005 | 20 | | PA | | 9-0 | 34-43-22 | D00393C | | | | D04919J | | 25 | | ALL |
| 006 | 20 | | PA | | 6-0 | 34-43-22 | GD00561 | D.. | 2 | | D04919J | | 22 | | 050-099, 150-199 |
| 006 | 20 | | PA | | 9-0 | 34-43-22 | GD00561 | D.. | 2 | | D04919J | | 22 | | 275-299 |
| 007 | 22 | | PA | | 9-0 | 34-43-22 | D00393B | | | | D04919J | | 1 | | ALL |
| 008 | 24 | | PK | | 37-0 | 34-43-21 | D00393B | | | | D04849J | | 1 | | ALL |
| 009 | 24 | | PK | | 27-0 | 34-43-22 | D00393B | | | | D00495 | | K | | ALL |
| 010 | 24 | | PK | | 27-0 | 34-43-22 | D00393B | | | | D00495 | | L | | ALL |
| 011 | 24 | | PK | | 27-0 | 34-43-22 | D00393B | | | | D00495 | | M | | ALL |
| 012 | 24 | | PK | | 27-0 | 34-43-22 | D00393B | | | | D00495 | | V | | 050-099, 151 |
| 012 | 24 | | PK | | 27-0 | 34-43-22 | SP09005 | | | W | D00495 | | V | | 150, 152-199, 275-299 |
| 013 | 24 | | PK | | 27-0 | 34-43-22 | D00393B | | | | D00495 | | U | | ALL |
| 014 | 24 | | PK | | 27-0 | 34-43-22 | D00393B | | | | D00495 | | F- | | ALL |
| 015 | 24 | | PK | | 31-0 | 34-43-22 | D00393B | | | | SP00005 | | | 9 | ALL |
| 017 | 24 | | PK | | 23-0 | 34-43-22 | D00495 | | | | SP00001 | | | 9 | ALL |
| 020 | 20 | | PA | | 10-0 | 34-43-22 | D00495 | | | | GD02464 | | D.. | 2 | ALL |
| 025 | 20 | | PA | | 12-0 | 34-43-22 | D00495 | | | | SP00341 | | | 9 | ALL |
| 026 | 20 | | UA | | 1-6 | 34-43-22 | D00495 | | | | GD04454 | | S.. | 2 | ALL |
| 201 | 20 | | UA | | 1-6 | 34-43-22 | D00393B | | | | GD00565 | | S.. | 2 | ALL |
| 201B | 22 | | PR | IA | 9-0 | 34-43-22 | D00393B | | | | D04919J | | | 18 | ALL |
| 201R | 22 | | PR | IA | 0-0 | 34-43-22 | D00393B | | | | D04919J | | | 17 | ALL |
| 201Z | | | | IA | 0-0 | 34-43-22 | D00393B | | | | D04919J | | FG | DED | ALL |
| 202B | 22 | | PR | IB | 9-0 | 34-43-22 | D00393B | | | | D04919J | | | 20 | ALL |
| 202R | 22 | | PR | IB | 0-0 | 34-43-22 | D00393B | | | | D04919J | | | 19 | ALL |
| 202Z | | | | IB | 0-0 | 34-43-22 | D00393B | | | | D04919J | | FG | DED | ALL |
| 203B | 22 | | PR | IC | 9-0 | 34-43-22 | D00393B | | | | D04919J | | | 14 | ALL |
| 203R | 22 | | PR | IC | 0-0 | 34-43-22 | D00393B | | | | D04919J | | | 13 | ALL |
| 203Z | | | | IC | 0-0 | 34-43-22 | D00393B | | | | D04919J | | FH | DED | ALL |
| 204B | 22 | | PR | ID | 9-0 | 34-43-22 | D00393B | | | | D04919J | | | 45 | ALL |
| 204R | 22 | | PR | ID | 0-0 | 34-43-22 | D00393B | | | | D04919J | | | 44 | ALL |
| 204Z | | | | ID | 0-0 | 34-43-22 | D00393B | | | | D04919J | | FH | DED | ALL |
| 205 | 20 | | UA | | 1-6 | 34-43-22 | D00393B | | | | GD00565 | | S.. | 2 | ALL |
| 205B | 22 | | PR | IE | 9-0 | 34-43-22 | D00393B | | | | D04919J | | | 16 | ALL |
| 205R | 22 | | PR | IE | 0-0 | 34-43-22 | D00393B | | | | D04919J | | | 15 | ALL |
| 205Z | | | | IE | 0-0 | 34-43-22 | D00393B | | | | D04919J | | FH | DED | ALL |
| 206 | 20 | | UA | | 1-6 | 34-43-21 | D00393B | | | | GD00565 | | S.. | 2 | ALL |
| 206B | 24 | | PW | IF | 37-0 | 34-43-21 | D00393B | | | | D04849J | | | 3 | ALL |
| 206R | 24 | | PW | IF | 0-0 | 34-43-21 | D00393B | | | | D04849J | | | 2 | ALL |

WIRE LIST
D280T132

91-21-11
Section W0800
Page 14
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|-------|---------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0803 | 286T0803 | | | WEATHER RADAR R (continued) | | | | | | | | | | | |
| 206Z | | | | IF | 0-0 | 34-43-21 | D00393B | | | | FN | D04849J | 4 | | ALL |
| 207W | 24 | 7K | | IG | 0-0 | 34-43-21 | D00393B | G02 | | | | TB0203F | A002 | 2 | ALL |
| 207WB | 24 | 7K | | IG | 0-6 | 34-43-21 | D00393B | G03 | | | | TB0203F | C002 | 2 | ALL |
| 207Z | | | | IG | 0-0 | 34-43-21 | D00393B | DED | | | | TB0203F | | | FA ALL |
| 208W | 24 | 7K | | IH | 37-0 | 34-43-21 | TB0203F | A002 | 2 | | | D04849J | 5 | | ALL |
| 208WB | 24 | 7K | | IH | 0-0 | 34-43-21 | TB0203F | C002 | 2 | | | D04849J | 6 | | ALL |
| 208Z | | | | IH | 0-0 | 34-43-21 | TB0203F | | | | FB | D04849J | 7 | | ALL |
| 209W | 24 | 7K | | II | 0-0 | 34-43-21 | D00393B | D02 | | | | TB0203F | A003 | 2 | ALL |
| 209WB | 24 | 7K | | II | 0-6 | 34-43-21 | D00393B | D03 | | | | TB0203F | C003 | 2 | ALL |
| 209Z | | | | II | 0-0 | 34-43-21 | D00393B | DED | | | | TB0203F | | | FC ALL |
| 210W | 24 | 7K | | IJ | 35-0 | 34-43-21 | TB0203F | A003 | 2 | | | D05365J | 1 | | 050-099, 151 |
| 210WB | 24 | 7K | | IJ | 35-0 | 34-43-21 | TB0203F | A003 | 2 | | | D05365J | 7 | | 150, 152-199, 275-299 |
| 210WB | 24 | 7K | | IJ | 0-0 | 34-43-21 | TB0203F | C003 | 2 | | | D05365J | 2 | | 050-099, 151 |
| 210WB | 24 | 7K | | IJ | 0-0 | 34-43-21 | TB0203F | C003 | 2 | | | D05365J | 8 | | 150, 152-199, 275-299 |
| 210Z | | | | IJ | 0-0 | 34-43-21 | TB0203F | | | | FD | D05365J | 3 | | 050-099, 151 |
| 210Z | | | | IJ | 0-0 | 34-43-21 | GD00043 | S.. | 2 | | | D05365J | 9 | | 150, 152-199, 275-299 |
| 211 | 20 | UA | | IK | 1-6 | 34-43-21 | D00393B | | | | FL | GD00565 | S.. | 2 | ALL |
| 211B | 24 | PW | | IK | 35-0 | 34-43-21 | D00393B | B04 | | | | D05365J | 5 | | ALL |
| 211R | 24 | PW | | IK | 0-0 | 34-43-21 | D00393B | B03 | | | | D05365J | 4 | | ALL |
| 211Z | | | | IK | 0-0 | 34-43-21 | D00393B | | | | FL | D05365J | 6 | | ALL |
| 212 | 20 | UA | | IL | 1-6 | 34-43-21 | D00393B | | | | FM | GD00565 | S.. | 2 | ALL |
| 212B | 24 | PW | | IL | 37-0 | 34-43-21 | D00393B | J12 | | | | D04849J | 9 | | ALL |
| 212R | 24 | PW | | IL | 0-0 | 34-43-21 | D00393B | J11 | | | | D04849J | 8 | | ALL |
| 212Z | | | | IL | 0-0 | 34-43-21 | D00393B | | | | FM | D04849J | 10 | | ALL |
| 213 | 20 | UA | | IM | 1-6 | 34-43-21 | D00393B | | | | FK | GD00565 | S.. | 2 | ALL |
| 213B | 24 | PW | | IM | 35-0 | 34-43-21 | D00393B | G13 | | | | D05365J | 12 | | ALL |
| 213R | 24 | PW | | IM | 0-0 | 34-43-21 | D00393B | G12 | | | | D05365J | 11 | | ALL |
| 213Z | | | | IM | 0-0 | 34-43-21 | D00393B | | | | FK | D05365J | 13 | | ALL |
| 214 | 20 | UA | | IN | 1-6 | 34-43-22 | D00393B | | | | FJ | GD00565 | S.. | 2 | ALL |
| 214B | 24 | PW | | IN | 27-0 | 34-43-22 | D00393B | B08 | | | | D00495 | J- | | ALL |
| 214R | 24 | PW | | IN | 0-0 | 34-43-22 | D00393B | B07 | | | | D00495 | H- | | ALL |
| 214Z | | | | IN | 0-0 | 34-43-22 | D00393B | | | | FJ | D00495 | | | FI ALL |
| 301B | 22 | PS | | MA | 9-0 | 34-43-22 | D00393B | C11 | | | | D04919J | 53 | | ALL |
| 301R | 22 | PS | | MA | 0-0 | 34-43-22 | D00393B | C10 | | | | D04919J | 52 | | ALL |
| 301Y | 22 | PS | | MA | 0-0 | 34-43-22 | D00393B | C12 | | | | D04919J | 54 | | ALL |
| 301Z | | | | MA | 0-0 | 34-43-22 | D00393B | | | | FG | D04919J | DED | | ALL |
| 302B | 22 | PS | | MB | 9-0 | 34-43-22 | D00393B | E11 | | | | D04919J | 39 | | ALL |
| 302R | 22 | PS | | MB | 0-0 | 34-43-22 | D00393B | E10 | | | | D04919J | 40 | | ALL |
| 302Y | 22 | PS | | MB | 0-0 | 34-43-22 | D00393B | E12 | | | | D04919J | 38 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0803 | 286T0803 | | | WEATHER RADAR R (continued) | | | | | | | | | | | |
| 302Z | | | | MB | 0-0 | 34-43-22 | D00393B | | | FG | D04919J | DED | | | ALL |
| 303B | 22 | PS | | MC | 9-0 | 34-43-22 | D00393B | A11 | | | D04919J | 42 | | | ALL |
| 303R | 22 | PS | | MC | 0-0 | 34-43-22 | D00393B | A10 | | | D04919J | 41 | | | ALL |
| 303Y | 22 | PS | | MC | 0-0 | 34-43-22 | D00393B | A12 | | | D04919J | 43 | | | ALL |
| 303Z | | | | MC | 0-0 | 34-43-22 | D00393B | | | FH | D04919J | DED | | | ALL |
| 901 | 24 | PK | | | 10-0 | 34-43-22 | SP09005 | | W | | D00393B | B06 | | | 150, 152-199, 275-299 |
| FRA | | | | | 0-4 | 34-43-21 | TB0203F | | | FA | GD00043 | S.. | 2 | | 050-099, 150-199 |
| FRA | | | | | 0-3 | 34-43-21 | TB0203F | | | FA | GD00043 | S.. | 2 | | 275-299 |
| FRB | | | | | 0-4 | 34-43-21 | TB0203F | | | FB | GD00043 | S.. | 2 | | 050-099, 150-199 |
| FRB | | | | | 0-3 | 34-43-21 | TB0203F | | | FB | GD00043 | S.. | 2 | | 275-299 |
| FRC | | | | | 0-4 | 34-43-21 | TB0203F | | | FC | GD00043 | S.. | 2 | | 050-099, 150-199 |
| FRC | | | | | 0-3 | 34-43-21 | TB0203F | | | FC | GD00043 | S.. | 2 | | 275-299 |
| FRD | | | | | 0-4 | 34-43-21 | TB0203F | | | FD | GD00043 | S.. | 2 | | 050-099, 151 |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS, MID RIGHT | | | | | | | | | | | |
| 001 | 18 | PA | | | 18-9 | 33-24-14 | D05166P | | 4 | | SM00047 | | S | | 050-099 |
| 001 | 18 | PA | | | 19-2 | 33-24-14 | D05166P | | 4 | | SM00045 | | S | | 150-199 |
| 001 | 18 | PA | | | 17-0 | 33-24-14 | D05166P | | 4 | | SM00045 | | S | | 275-278 |
| 001 | 18 | PA | | | 17-3 | 33-24-14 | D05166P | | 4 | | SM00045 | | S | | 280-299 |
| 002 | 18 | PA | | | 18-9 | 33-24-14 | D05166P | | 7 | | SM00048 | | S | | 050-099 |
| 002 | 18 | PA | | | 19-2 | 33-24-14 | D05166P | | 7 | | SM00046 | | S | | 150-199 |
| 002 | 18 | PA | | | 17-0 | 33-24-14 | D05166P | | 7 | | SM00046 | | S | | 275-278 |
| 002 | 18 | PA | | | 17-3 | 33-24-14 | D05166P | | 7 | | SM00046 | | S | | 280-299 |
| 003 | 20 | PA | | | 2-6 | 33-24-14 | SM00046 | | | S | D03304 | 3 | | | 150-157 |
| 003 | 20 | PA | | | 1-11 | 33-24-14 | SM00046 | | | S | D03304 | 3 | | | 275-278 |
| 003 | 20 | PA | | | 2-0 | 33-24-14 | SM00046 | | | S | D03304 | 3 | | | 280-299 |
| 004 | 20 | PA | | | 2-6 | 33-24-14 | SM00045 | | | S | D03304 | 4 | | | 150-157 |
| 004 | 20 | PA | | | 1-11 | 33-24-14 | SM00045 | | | S | D03304 | 4 | | | 275-278 |
| 004 | 20 | PA | | | 2-0 | 33-24-14 | SM00045 | | | S | D03304 | 4 | | | 280-299 |
| 005 | 20 | PA | | | 2-5 | 33-24-14 | GD05642 | | A.. | E | D03304 | 5 | | | 150-157 |
| 005 | 20 | PA | | | 1-11 | 33-24-14 | GD05152 | | A.. | E | D03304 | 5 | | | 275-278 |
| 005 | 20 | PA | | | 1-9 | 33-24-14 | GD05152 | | A.. | E | D03304 | 5 | | | 280-299 |
| 006 | 18 | PA | | | 3-1 | 33-24-14 | SM00045 | | | S | SM00049 | | S | | 275-278 |
| 006 | 18 | PA | | | 4-4 | 33-24-14 | SM00045 | | | S | SM00049 | | S | | 280-299 |
| 007 | 18 | PA | | | 3-1 | 33-24-14 | SM00046 | | | S | SM00050 | | S | | 275-278 |
| 007 | 18 | PA | | | 4-4 | 33-24-14 | SM00046 | | | S | SM00050 | | S | | 280-299 |
| 008 | 22 | PA | | | 2-7 | 33-24-14 | SM00048 | | | S | D03306 | 3 | | | 050-099 |
| 008 | 20 | PA | | | 1-8 | 33-24-14 | SM00046 | | | S | D03306 | 3 | | | 150-199 |
| 008 | 20 | PA | | | 1-7 | 33-24-14 | SM00050 | | | S | D03306 | 3 | | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 16

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | | |
| 008 | 20 | | PA | 2-3 | 33-24-14 | SM00050 | | | | | | S | D03306 | 3 | | 280-299 |
| 009 | 22 | | PA | 2-7 | 33-24-14 | SM00047 | | | | | | S | D03306 | 4 | | 050-099 |
| 009 | 20 | | PA | 1-8 | 33-24-14 | SM00045 | | | | | | S | D03306 | 4 | | 150-199 |
| 009 | 20 | | PA | 1-7 | 33-24-14 | SM00049 | | | | | | S | D03306 | 4 | | 275-278 |
| 009 | 20 | | PA | 2-3 | 33-24-14 | SM00049 | | | | | | S | D03306 | 4 | | 280-299 |
| 010 | 20 | | PA | 6-0 | 33-24-14 | GD02310 | | | | A.. | | E | D03306 | 5 | | 050-099 |
| 010 | 20 | | PA | 2-8 | 33-24-14 | GD05642 | | | | A.. | | E | D03306 | 5 | | 150-157 |
| 010 | 20 | | PA | 6-1 | 33-24-14 | GD02310 | | | | A.. | | E | D03306 | 5 | | 162-199 |
| 010 | 20 | | PA | 3-7 | 33-24-14 | GD05152 | | | | A.. | | E | D03306 | 5 | | 275-278 |
| 010 | 20 | | PA | 3-2 | 33-24-14 | GD05152 | | | | A.. | | E | D03306 | 5 | | 280-299 |
| 011 | 18 | | PA | 7-3 | 33-24-14 | SM00047 | | | | | | S | SM00053 | | S | 050-099 |
| 011 | 18 | | PA | 2-2 | 33-24-14 | SM00045 | | | | | | S | SM00049 | | S | 150-199 |
| 012 | 18 | | PA | 7-3 | 33-24-14 | SM00048 | | | | | | S | SM00054 | | S | 050-099 |
| 012 | 18 | | PA | 2-2 | 33-24-14 | SM00046 | | | | | | S | SM00050 | | S | 150-199 |
| 013 | 22 | | PA | 3-9 | 33-24-14 | SM00048 | | | | | | S | D03308 | 3 | | 050-099 |
| 013 | 20 | | PA | 1-7 | 33-24-14 | SM00050 | | | | | | S | D03308 | 3 | | 150-199 |
| 013 | 20 | | PA | 3-0 | 33-24-14 | SM00050 | | | | | | S | D03308 | 3 | | 275-278 |
| 013 | 20 | | PA | 1-11 | 33-24-14 | SM00050 | | | | | | S | D03308 | 3 | | 280-299 |
| 014 | 22 | | PA | 3-9 | 33-24-14 | SM00047 | | | | | | S | D03308 | 4 | | 050-099 |
| 014 | 20 | | PA | 1-7 | 33-24-14 | SM00049 | | | | | | S | D03308 | 4 | | 150-199 |
| 014 | 20 | | PA | 3-0 | 33-24-14 | SM00049 | | | | | | S | D03308 | 4 | | 275-278 |
| 014 | 20 | | PA | 1-11 | 33-24-14 | SM00049 | | | | | | S | D03308 | 4 | | 280-299 |
| 015 | 20 | | PA | 4-4 | 33-24-14 | GD02310 | | | | A.. | | E | D03308 | 5 | | 050-099 |
| 015 | 20 | | PA | 4-5 | 33-24-14 | GD02310 | | | | A.. | | E | D03308 | 5 | | 150-199 |
| 015 | 20 | | PA | 4-3 | 33-24-14 | GD02310 | | | | A.. | | E | D03308 | 5 | | 275-278 |
| 015 | 20 | | PA | 4-2 | 33-24-14 | GD02310 | | | | A.. | | E | D03308 | 5 | | 280-299 |
| 016 | 18 | | PA | 5-10 | 33-24-14 | SM00049 | | | | | | S | SM00053 | | S | 150-199 |
| 016 | 18 | | PA | 6-11 | 33-24-14 | SM00049 | | | | | | S | SM00053 | | S | 275-278 |
| 016 | 18 | | PA | 4-8 | 33-24-14 | SM00049 | | | | | | S | SM00053 | | S | 280-299 |
| 017 | 18 | | PA | 5-10 | 33-24-14 | SM00050 | | | | | | S | SM00054 | | S | 150-199 |
| 017 | 18 | | PA | 6-11 | 33-24-14 | SM00050 | | | | | | S | SM00054 | | S | 275-278 |
| 017 | 18 | | PA | 4-8 | 33-24-14 | SM00050 | | | | | | S | SM00054 | | S | 280-299 |
| 018 | 22 | | PA | 1-11 | 33-24-14 | SM00054 | | | | | | S | D03310 | 3 | | 050-099 |
| 018 | 20 | | PA | 3-0 | 33-24-14 | SM00054 | | | | | | S | D03310 | 3 | | 150-199 |
| 018 | 20 | | PA | 2-10 | 33-24-14 | SM00054 | | | | | | S | D03310 | 3 | | 275-278 |
| 018 | 20 | | PA | 1-8 | 33-24-14 | SM00054 | | | | | | S | D03310 | 3 | | 280-299 |
| 019 | 22 | | PA | 1-11 | 33-24-14 | SM00053 | | | | | | S | D03310 | 4 | | 050-099 |
| 019 | 20 | | PA | 3-0 | 33-24-14 | SM00053 | | | | | | S | D03310 | 4 | | 150-199 |
| 019 | 20 | | PA | 2-10 | 33-24-14 | SM00053 | | | | | | S | D03310 | 4 | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 17

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | |
| 019 | 20 | | PA | | 1-8 | 33-24-14 | SM00053 | | S | | D03310 | | 4 | | 280-299 |
| 020 | 20 | | PA | | 1-9 | 33-24-14 | GD02310 | A.. | E | | D03310 | | 5 | | 050-099 |
| 020 | 20 | | PA | | 1-10 | 33-24-14 | GD02310 | A.. | E | | D03310 | | 5 | | 150-199, 275-278 |
| 020 | 20 | | PA | | 1-8 | 33-24-14 | GD02310 | A.. | E | | D03310 | | 5 | | 280-299 |
| 023 | 22 | | PA | | 2-7 | 33-24-14 | SM00054 | | S | | D03312 | | 3 | | 050-099 |
| 023 | 20 | | PA | | 1-9 | 33-24-14 | SM00054 | | S | | D03312 | | 3 | | 150-199 |
| 023 | 20 | | PA | | 1-8 | 33-24-14 | SM00054 | | S | | D03312 | | 3 | | 275-278 |
| 023 | 20 | | PA | | 2-11 | 33-24-14 | SM00054 | | S | | D03312 | | 3 | | 280-299 |
| 024 | 22 | | PA | | 2-7 | 33-24-14 | SM00053 | | S | | D03312 | | 4 | | 050-099 |
| 024 | 20 | | PA | | 1-9 | 33-24-14 | SM00053 | | S | | D03312 | | 4 | | 150-199 |
| 024 | 20 | | PA | | 1-8 | 33-24-14 | SM00053 | | S | | D03312 | | 4 | | 275-278 |
| 024 | 20 | | PA | | 2-11 | 33-24-14 | SM00053 | | S | | D03312 | | 4 | | 280-299 |
| 025 | 20 | | PA | | 4-0 | 33-24-14 | GD02310 | A.. | E | | D03312 | | 5 | | 050-099 |
| 025 | 20 | | PA | | 3-11 | 33-24-14 | GD02310 | A.. | E | | D03312 | | 5 | | 150-199 |
| 025 | 20 | | PA | | 3-8 | 33-24-14 | GD02310 | A.. | E | | D03312 | | 5 | | 275-278 |
| 025 | 20 | | PA | | 3-10 | 33-24-14 | GD02310 | A.. | E | | D03312 | | 5 | | 280-299 |
| 026 | 18 | | PA | | 5-8 | 33-24-14 | SM00053 | | S | | SM00057 | | | S | 050-099 |
| 026 | 18 | | PA | | 5-11 | 33-24-14 | SM00053 | | S | | SM00057 | | | S | 150-199, 275-278 |
| 026 | 18 | | PA | | 7-1 | 33-24-14 | SM00053 | | S | | SM00057 | | | S | 280-299 |
| 027 | 18 | | PA | | 5-8 | 33-24-14 | SM00054 | | S | | SM00058 | | | S | 050-099 |
| 027 | 18 | | PA | | 5-11 | 33-24-14 | SM00054 | | S | | SM00058 | | | S | 150-199, 275-278 |
| 027 | 18 | | PA | | 7-1 | 33-24-14 | SM00054 | | S | | SM00058 | | | S | 280-299 |
| 028 | 22 | | PA | | 1-11 | 33-24-14 | SM00058 | | S | | D03314 | | 3 | | 050-099 |
| 028 | 20 | | PA | | 3-1 | 33-24-14 | SM00058 | | S | | D03314 | | 3 | | 150-199 |
| 028 | 20 | | PA | | 2-9 | 33-24-14 | SM00058 | | S | | D03314 | | 3 | | 275-278 |
| 028 | 20 | | PA | | 2-10 | 33-24-14 | SM00058 | | S | | D03314 | | 3 | | 280-299 |
| 029 | 22 | | PA | | 1-11 | 33-24-14 | SM00057 | | S | | D03314 | | 4 | | 050-099 |
| 029 | 20 | | PA | | 3-1 | 33-24-14 | SM00057 | | S | | D03314 | | 4 | | 150-199 |
| 029 | 20 | | PA | | 2-9 | 33-24-14 | SM00057 | | S | | D03314 | | 4 | | 275-278 |
| 029 | 20 | | PA | | 2-10 | 33-24-14 | SM00057 | | S | | D03314 | | 4 | | 280-299 |
| 030 | 20 | | PA | | 4-3 | 33-24-14 | GD02316 | A.. | E | | D03314 | | 5 | | 050-099, 275-278 |
| 030 | 20 | | PA | | 4-5 | 33-24-14 | GD02316 | A.. | E | | D03314 | | 5 | | 150-199 |
| 030 | 20 | | PA | | 4-2 | 33-24-14 | GD02316 | A.. | E | | D03314 | | 5 | | 280-299 |
| 033 | 22 | | PA | | 2-11 | 33-24-14 | SM00058 | | S | | D03316 | | 3 | | 050-099 |
| 033 | 20 | | PA | | 1-11 | 33-24-14 | SM00058 | | S | | D03316 | | 3 | | 150-199 |
| 033 | 20 | | PA | | 2-2 | 33-24-14 | SM00058 | | S | | D03316 | | 3 | | 275-278 |
| 033 | 20 | | PA | | 2-1 | 33-24-14 | SM00058 | | S | | D03316 | | 3 | | 280-299 |
| 034 | 22 | | PA | | 2-11 | 33-24-14 | SM00057 | | S | | D03316 | | 4 | | 050-099 |
| 034 | 20 | | PA | | 1-11 | 33-24-14 | SM00057 | | S | | D03316 | | 4 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 18

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | | |
| 034 | 20 | PA | | 2-2 | 33-24-14 | SM00057 | | S | | D03316 | 4 | | | 275-278 | | |
| 034 | 20 | PA | | 2-1 | 33-24-14 | SM00057 | | S | | D03316 | 4 | | | 280-299 | | |
| 035 | 20 | PA | | 1-9 | 33-24-14 | GD02316 | | A.. | E | D03316 | 5 | | | 050-099, 275-278 | | |
| 035 | 20 | PA | | 1-10 | 33-24-14 | GD02316 | | A.. | E | D03316 | 5 | | | 150-199 | | |
| 035 | 20 | PA | | 1-7 | 33-24-14 | GD02316 | | A.. | E | D03316 | 5 | | | 280-299 | | |
| 036 | 18 | PA | | 6-1 | 33-24-14 | SM00057 | | S | | SM00061 | | S | | 050-099 | | |
| 036 | 18 | PA | | 4-10 | 33-24-14 | SM00057 | | S | | SM00061 | | S | | 150-199, 280-299 | | |
| 036 | 18 | PA | | 5-1 | 33-24-14 | SM00057 | | S | | SM00061 | | S | | 275-278 | | |
| 037 | 18 | PA | | 6-1 | 33-24-14 | SM00058 | | S | | SM00062 | | S | | 050-099 | | |
| 037 | 18 | PA | | 4-10 | 33-24-14 | SM00058 | | S | | SM00062 | | S | | 150-199, 280-299 | | |
| 037 | 18 | PA | | 5-1 | 33-24-14 | SM00058 | | S | | SM00062 | | S | | 275-278 | | |
| 038 | 22 | PA | | 1-11 | 33-24-14 | D03318 | | 3 | | SM00062 | | S | | 050-099 | | |
| 038 | 20 | PA | | 2-0 | 33-24-14 | SM00062 | | S | | D03318 | 3 | | | 150-199, 280-299 | | |
| 038 | 20 | PA | | 2-1 | 33-24-14 | SM00062 | | S | | D03318 | 3 | | | 275-278 | | |
| 039 | 22 | PA | | 1-11 | 33-24-14 | D03318 | | 4 | | SM00061 | | S | | 050-099 | | |
| 039 | 20 | PA | | 2-0 | 33-24-14 | SM00061 | | S | | D03318 | 4 | | | 150-199, 280-299 | | |
| 039 | 20 | PA | | 2-1 | 33-24-14 | SM00061 | | S | | D03318 | 4 | | | 275-278 | | |
| 040 | 22 | PA | | 3-10 | 33-24-14 | D03318 | | 5 | | GD02316 | | A.. | E | 050-099 | | |
| 040 | 20 | PA | | 4-0 | 33-24-14 | GD02316 | | A.. | E | D03318 | 5 | | | 150-199 | | |
| 040 | 20 | PA | | 3-11 | 33-24-14 | GD02316 | | A.. | E | D03318 | 5 | | | 275-278 | | |
| 040 | 20 | PA | | 3-9 | 33-24-14 | GD02316 | | A.. | E | D03318 | 5 | | | 280-299 | | |
| 043 | 22 | PA | | 2-9 | 33-24-14 | SM00062 | | S | | D03320 | 3 | | | 050-099 | | |
| 043 | 20 | PA | | 3-0 | 33-24-14 | SM00062 | | S | | D03320 | 3 | | | 150-199 | | |
| 043 | 20 | PA | | 2-11 | 33-24-14 | SM00062 | | S | | D03320 | 3 | | | 275-278 | | |
| 043 | 20 | PA | | 3-1 | 33-24-14 | SM00062 | | S | | D03320 | 3 | | | 280-299 | | |
| 044 | 22 | PA | | 2-9 | 33-24-14 | SM00061 | | S | | D03320 | 4 | | | 050-099 | | |
| 044 | 20 | PA | | 3-0 | 33-24-14 | SM00061 | | S | | D03320 | 4 | | | 150-199 | | |
| 044 | 20 | PA | | 2-11 | 33-24-14 | SM00061 | | S | | D03320 | 4 | | | 275-278 | | |
| 044 | 20 | PA | | 3-1 | 33-24-14 | SM00061 | | S | | D03320 | 4 | | | 280-299 | | |
| 045 | 20 | PA | | 4-3 | 33-24-14 | GD02322 | | A.. | E | D03320 | 5 | | | 050-099 | | |
| 045 | 20 | PA | | 4-5 | 33-24-14 | GD05036 | | A.. | E | D03320 | 5 | | | 150-199 | | |
| 045 | 20 | PA | | 4-4 | 33-24-14 | GD05036 | | A.. | E | D03320 | 5 | | | 275-278 | | |
| 045 | 20 | PA | | 15-0 | 33-24-14 | GD01592 | | A.. | E | D03320 | 5 | | | 280-299 | | |
| 046 | 18 | PA | | 7-1 | 33-24-14 | SM00061 | | S | | SM00065 | | S | | 050-099 | | |
| 046 | 18 | PA | | 6-8 | 33-24-14 | SM00061 | | S | | SM00147 | | S | | 150-199 | | |
| 046 | 18 | PA | | 6-11 | 33-24-14 | SM00061 | | S | | SM00147 | | S | | 275-278 | | |
| 046 | 18 | PA | | 7-1 | 33-24-14 | SM00061 | | S | | SM00147 | | S | | 280-299 | | |
| 047 | 18 | PA | | 7-1 | 33-24-14 | SM00062 | | S | | SM00066 | | S | | 050-099 | | |
| 047 | 18 | PA | | 6-8 | 33-24-14 | SM00062 | | S | | SM00148 | | S | | 150-199 | | |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 19

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | | |
| 047 | 18 | PA | | 6-11 | 33-24-14 | SM00062 | | S | | SM00148 | | S | | 275-278 | | |
| 047 | 18 | PA | | 7-1 | 33-24-14 | SM00062 | | S | | SM00148 | | S | | 280-299 | | |
| 048 | 22 | PA | | 2-10 | 33-24-14 | SM00066 | | S | | D03322 | 3 | | | 050-099 | | |
| 048 | 20 | PA | | 1-8 | 33-24-14 | SM00064 | | S | | D03322 | 3 | | | 275-278 | | |
| 048 | 20 | PA | | 2-3 | 33-24-14 | SM00064 | | S | | D03322 | 3 | | | 280-299 | | |
| 049 | 22 | PA | | 2-10 | 33-24-14 | SM00065 | | S | | D03322 | 4 | | | 050-099 | | |
| 049 | 20 | PA | | 1-8 | 33-24-14 | SM00063 | | S | | D03322 | 4 | | | 275-278 | | |
| 049 | 20 | PA | | 2-3 | 33-24-14 | SM00063 | | S | | D03322 | 4 | | | 280-299 | | |
| 050 | 20 | PA | | 1-7 | 33-24-14 | GD02322 | | A.. | E | D03322 | 5 | | | 050-099 | | |
| 050 | 20 | PA | | 3-4 | 33-24-14 | GD05040 | | A.. | E | D03322 | 5 | | | 275-278 | | |
| 050 | 20 | PA | | 3-11 | 33-24-14 | GD05040 | | A.. | E | D03322 | 5 | | | 280-299 | | |
| 051 | 18 | PA | | 4-6 | 33-24-14 | SM00069 | | S | | D06516J | 4 | DK | | 150-199 | | |
| 051 | 18 | PA | | 3-6 | 33-24-14 | SM00063 | | S | | D06516J | 4 | DK | | 275-278 | | |
| 051 | 18 | PA | | 1-8 | 33-24-14 | SM00063 | | S | | D06516J | 4 | DK | | 280-299 | | |
| 052 | 18 | PA | | 4-6 | 33-24-14 | SM00070 | | S | | D06516J | 3 | DK | | 150-199 | | |
| 052 | 18 | PA | | 3-6 | 33-24-14 | SM00064 | | S | | D06516J | 3 | DK | | 275-278 | | |
| 052 | 18 | PA | | 1-8 | 33-24-14 | SM00064 | | S | | D06516J | 3 | DK | | 280-299 | | |
| 053 | 22 | PA | | 1-7 | 33-24-14 | SM00066 | | S | | D03324 | 3 | | | 050-099 | | |
| 053 | 20 | PA | | 3-0 | 33-24-14 | D03324 | | | 3 | SM00066 | | S | | 150-154, 162-163 | | |
| 053 | 20 | PA | | 1-7 | 33-24-14 | D03324 | | | 3 | SM00152 | | S | | 155-157, 164-199 | | |
| 054 | 22 | PA | | 1-7 | 33-24-14 | SM00065 | | S | | D03324 | 4 | | | 050-099 | | |
| 054 | 20 | PA | | 3-0 | 33-24-14 | D03324 | | | 4 | SM00065 | | S | | 150-154, 162-163 | | |
| 054 | 20 | PA | | 1-7 | 33-24-14 | D03324 | | | 4 | SM00151 | | S | | 155-157, 164-199 | | |
| 055 | 20 | PA | | 3-9 | 33-24-14 | GD02322 | | A.. | E | D03324 | 5 | | | 050-099 | | |
| 055 | 20 | PA | | 4-0 | 33-24-14 | D03324 | | | 5 | GD05634 | | A.. | E | 150-199 | | |
| 056 | 18 | PA | | 5-11 | 33-24-14 | SM00065 | | S | | SM00069 | | S | | 050-099 | | |
| 056 | 18 | PA | | 1-1 | 33-24-14 | SM00065 | | S | | SM00069 | | S | | 150-154, 162-163 | | |
| 056 | 18 | PA | | 3-2 | 33-24-14 | SM00151 | | S | | SM00069 | | S | | 155-157, 164-199 | | |
| 057 | 18 | PA | | 5-11 | 33-24-14 | SM00066 | | S | | SM00070 | | S | | 050-099 | | |
| 057 | 18 | PA | | 1-1 | 33-24-14 | SM00066 | | S | | SM00070 | | S | | 150-154, 162-163 | | |
| 057 | 18 | PA | | 2-8 | 33-24-14 | SM00152 | | S | | SM00070 | | S | | 155-157, 164-199 | | |
| 058 | 22 | PA | | 3-1 | 33-24-14 | SM00070 | | S | | D03326 | 3 | | | 050-099 | | |
| 058 | 20 | PA | | 2-6 | 33-24-14 | D03326 | | | 3 | SM00070 | | S | | 150-199 | | |
| 059 | 22 | PA | | 3-1 | 33-24-14 | SM00069 | | S | | D03326 | 4 | | | 050-099 | | |
| 059 | 20 | PA | | 2-6 | 33-24-14 | D03326 | | | 4 | SM00069 | | S | | 150-199 | | |
| 060 | 20 | PA | | 4-4 | 33-24-14 | GD02324 | | A.. | E | D03326 | 5 | | | 050-099 | | |
| 060 | 20 | PA | | 2-7 | 33-24-14 | D03326 | | | 5 | GD05634 | | A.. | E | 150-199 | | |
| 063 | 22 | PA | | 1-8 | 33-24-14 | SM00070 | | S | | D03328 | 3 | | | 050-099 | | |
| 064 | 22 | PA | | 1-8 | 33-24-14 | SM00069 | | S | | D03328 | 4 | | | 050-099 | | |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 20

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | | |
| 065 | 20 | | PA | 1-9 | 33-24-14 | GD02324 | A.. | E | | D03328 | 5 | | | 050-099 | | |
| 066 | 18 | | PA | 2-2 | 33-24-14 | SM00069 | | S | | SM00071 | | S | | 050-099 | | |
| 067 | 18 | | PA | 2-2 | 33-24-14 | SM00070 | | S | | SM00072 | | S | | 050-099 | | |
| 068 | 22 | | PA | 3-0 | 33-24-14 | SM00072 | | S | | D03330 | 3 | | | 050-099 | | |
| 069 | 22 | | PA | 3-0 | 33-24-14 | SM00071 | | S | | D03330 | 4 | | | 050-099 | | |
| 070 | 20 | | PA | 3-10 | 33-24-14 | GD02324 | A.. | E | | D03330 | 5 | | | 050-099 | | |
| 071 | 18 | | PA | 23-11 | 33-24-14 | SM00071 | | S | | SM00077 | | S | | 050-099 | | |
| 072 | 18 | | PA | 23-11 | 33-24-14 | SM00072 | | S | | SM00078 | | S | | 050-099 | | |
| 083 | 22 | | PA | 2-11 | 33-24-14 | SM00078 | | S | | D03336 | 3 | | | 050-099 | | |
| 084 | 22 | | PA | 2-11 | 33-24-14 | SM00077 | | S | | D03336 | 4 | | | 050-099 | | |
| 085 | 20 | | PA | 4-1 | 33-24-14 | GD02334 | A.. | E | | D03336 | 5 | | | 050-099 | | |
| 086 | 18 | | PA | 3-2 | 33-24-14 | SM00077 | | S | | SM00081 | | S | | 050-099 | | |
| 087 | 18 | | PA | 3-2 | 33-24-14 | SM00078 | | S | | SM00082 | | S | | 050-099 | | |
| 088 | 22 | | PA | 2-7 | 33-24-14 | SM00082 | | S | | D03338 | 3 | | | 050-099 | | |
| 089 | 22 | | PA | 2-7 | 33-24-14 | SM00081 | | S | | D03338 | 4 | | | 050-099 | | |
| 090 | 20 | | PA | 1-8 | 33-24-14 | GD02334 | A.. | E | | D03338 | 5 | | | 050-099 | | |
| 093 | 22 | | PA | 2-1 | 33-24-14 | SM00082 | | S | | D03340 | 3 | | | 050-099 | | |
| 094 | 22 | | PA | 2-1 | 33-24-14 | SM00081 | | S | | D03340 | 4 | | | 050-099 | | |
| 095 | 20 | | PA | 4-2 | 33-24-14 | GD02334 | A.. | E | | D03340 | 5 | | | 050-099 | | |
| 096 | 18 | | PA | 5-3 | 33-24-14 | SM00081 | | S | | SM00085 | | S | | 050-099 | | |
| 097 | 18 | | PA | 5-3 | 33-24-14 | SM00082 | | S | | SM00086 | | S | | 050-099 | | |
| 098 | 22 | | PA | 3-0 | 33-24-14 | SM00086 | | S | | D03342 | 3 | | | 050-099 | | |
| 099 | 22 | | PA | 3-0 | 33-24-14 | SM00085 | | S | | D03342 | 4 | | | 050-099 | | |
| 100 | 20 | | PA | 6-0 | 33-24-14 | GD02334 | A.. | E | | D03342 | 5 | | | 050-099 | | |
| 103 | 22 | | PA | 1-9 | 33-24-14 | SM00086 | | S | | D03344 | 3 | | | 050-099 | | |
| 104 | 22 | | PA | 1-9 | 33-24-14 | SM00085 | | S | | D03344 | 4 | | | 050-099 | | |
| 105 | 20 | | PA | 1-10 | 33-24-14 | GD02340 | A.. | E | | D03344 | 5 | | | 050-099 | | |
| 106 | 18 | | PA | 2-4 | 33-24-14 | SM00085 | | S | | SM00087 | | S | | 050-099 | | |
| 107 | 18 | | PA | 2-4 | 33-24-14 | SM00086 | | S | | SM00088 | | S | | 050-099 | | |
| 108 | 22 | | PA | 2-11 | 33-24-14 | SM00088 | | S | | D03346 | 3 | | | 050-099 | | |
| 109 | 22 | | PA | 2-11 | 33-24-14 | SM00087 | | S | | D03346 | 4 | | | 050-099 | | |
| 110 | 20 | | PA | 3-10 | 33-24-14 | GD02340 | A.. | E | | D03346 | 5 | | | 050-099 | | |
| 111 | 18 | | PA | 17-7 | 33-24-14 | SM00087 | | S | | D05168P | 4 | | | 050-099 | | |
| 112 | 18 | | PA | 17-7 | 33-24-14 | SM00088 | | S | | D05168P | 7 | | | 050-099 | | |
| 115 | 20 | | PA | 3-5 | 33-24-14 | D03202 | | 4 | | SM00045 | | S | | 275-278 | | |
| 115 | 20 | | PA | 2-9 | 33-24-14 | D03202 | | 4 | | SM00045 | | S | | 280-299 | | |
| 116 | 20 | | PA | 3-5 | 33-24-14 | D03202 | | 3 | | SM00046 | | S | | 275-278 | | |
| 116 | 20 | | PA | 2-9 | 33-24-14 | D03202 | | 3 | | SM00046 | | S | | 280-299 | | |
| 117 | 20 | | PA | 4-5 | 33-24-14 | D03202 | | 5 | | GD05152 | | A.. | E | 275-278 | | |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 21

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | | | |
| 117 | 20 | | PA | | 4-1 | 33-24-14 | D03202 | | 5 | | | | GD05152 | A.. | E | | 280-299 |
| 201B | 22 | | PB | A | 19-11 | 23-31-17 | D05166P | | 2 | | | | SM00006 | | S | | 050-099 |
| 201B | 22 | | PB | A | 19-2 | 23-31-17 | D05166P | | 2 | | | | SM00092 | | S | | 150-157 |
| 201B | 22 | | PB | A | 20-3 | 23-31-17 | D05166P | | 2 | | | | SM00006 | | S | | 162-199 |
| 201B | 22 | | PB | A | 17-0 | 23-31-17 | D05166P | | 2 | | | | SM00092 | | S | | 275-278 |
| 201B | 22 | | PB | A | 17-3 | 23-31-17 | D05166P | | 2 | | | | SM00002 | | S | | 280-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-17 | D05166P | | 1 | | | | SM00005 | | S | | 050-099, 162-199 |
| 201R | 22 | | PB | A | 0-0 | 23-31-17 | D05166P | | 1 | | | | SM00091 | | S | | 150-157, 275-278 |
| 201R | 22 | | PB | A | 0-0 | 23-31-17 | D05166P | | 1 | | | | SM00001 | | S | | 280-299 |
| 202B | 22 | | PB | B | 2-6 | 23-31-17 | SM00092 | | | S | | | D03304 | 2 | | | 150-157 |
| 202B | 22 | | PB | B | 1-11 | 23-31-17 | SM00092 | | | S | | | D03304 | 2 | | | 275-278 |
| 202B | 22 | | PB | B | 2-0 | 23-31-17 | SM00002 | | | S | | | D03304 | 2 | | | 280-299 |
| 202R | 22 | | PB | B | 0-0 | 23-31-17 | SM00091 | | | S | | | D03304 | 1 | | | 150-157, 275-278 |
| 202R | 22 | | PB | B | 0-0 | 23-31-17 | SM00001 | | | S | | | D03304 | 1 | | | 280-299 |
| 203B | 22 | | PB | C | 2-2 | 23-31-17 | SM00092 | | | S | | | SM00006 | | S | | 150-157 |
| 203B | 22 | | PB | C | 3-1 | 23-31-17 | SM00092 | | | S | | | SM00006 | | S | | 275-278 |
| 203B | 22 | | PB | C | 4-2 | 23-31-17 | SM00002 | | | S | | | SM00006 | | S | | 280-299 |
| 203R | 22 | | PB | C | 0-0 | 23-31-17 | SM00091 | | | S | | | SM00005 | | S | | 150-157, 275-278 |
| 203R | 22 | | PB | C | 0-0 | 23-31-17 | SM00001 | | | S | | | SM00005 | | S | | 280-299 |
| 204B | 22 | | PB | D | 1-6 | 23-31-17 | SM00006 | | | S | | | D03306 | 2 | | | 050-099 |
| 204B | 22 | | PB | D | 1-11 | 23-31-17 | SM00006 | | | S | | | D03306 | 2 | | | 150-199 |
| 204B | 22 | | PB | D | 1-7 | 23-31-17 | SM00006 | | | S | | | D03306 | 2 | | | 275-278 |
| 204B | 22 | | PB | D | 2-3 | 23-31-17 | SM00006 | | | S | | | D03306 | 2 | | | 280-299 |
| 204R | 22 | | PB | D | 0-0 | 23-31-17 | SM00005 | | | S | | | D03306 | 1 | | | ALL |
| 206B | 22 | | PB | F | 2-8 | 23-31-17 | SM00006 | | | S | | | D03308 | 2 | | | 050-099 |
| 206B | 22 | | PB | F | 1-7 | 23-31-17 | SM00006 | | | S | | | D03308 | 2 | | | 150-199 |
| 206B | 22 | | PB | F | 3-0 | 23-31-17 | SM00006 | | | S | | | D03308 | 2 | | | 275-278 |
| 206B | 22 | | PB | F | 1-11 | 23-31-17 | SM00006 | | | S | | | D03308 | 2 | | | 280-299 |
| 206R | 22 | | PB | F | 0-0 | 23-31-17 | SM00005 | | | S | | | D03308 | 1 | | | ALL |
| 207B | 22 | | PB | G | 6-2 | 23-31-17 | SM00006 | | | S | | | SM00010 | | S | | 050-099 |
| 207B | 22 | | PB | G | 5-10 | 23-31-17 | SM00006 | | | S | | | SM00010 | | S | | 150-199 |
| 207B | 22 | | PB | G | 6-11 | 23-31-17 | SM00006 | | | S | | | SM00010 | | S | | 275-278 |
| 207B | 22 | | PB | G | 4-8 | 23-31-17 | SM00006 | | | S | | | SM00010 | | S | | 280-299 |
| 207R | 22 | | PB | G | 0-0 | 23-31-17 | SM00005 | | | S | | | SM00009 | | S | | ALL |
| 208B | 22 | | PB | H | 1-11 | 23-31-17 | SM00010 | | | S | | | D03310 | 2 | | | 050-099 |
| 208B | 22 | | PB | H | 3-0 | 23-31-17 | SM00010 | | | S | | | D03310 | 2 | | | 150-199 |
| 208B | 22 | | PB | H | 2-10 | 23-31-17 | SM00010 | | | S | | | D03310 | 2 | | | 275-278 |
| 208B | 22 | | PB | H | 1-8 | 23-31-17 | SM00010 | | | S | | | D03310 | 2 | | | 280-299 |
| 208R | 22 | | PB | H | 0-0 | 23-31-17 | SM00009 | | | S | | | D03310 | 1 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 22

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | |
| 210B | 22 | PB | K | 2-7 | 23-31-17 | SM00010 | | S | | D03312 | 2 | | | 050-099 | |
| 210B | 22 | PB | K | 1-9 | 23-31-17 | SM00010 | | S | | D03312 | 2 | | | 150-199 | |
| 210B | 22 | PB | K | 1-8 | 23-31-17 | SM00010 | | S | | D03312 | 2 | | | 275-278 | |
| 210B | 22 | PB | K | 2-11 | 23-31-17 | SM00010 | | S | | D03312 | 2 | | | 280-299 | |
| 210R | 22 | PB | K | 0-0 | 23-31-17 | SM00009 | | S | | D03312 | 1 | | | ALL | |
| 211B | 22 | PB | L | 5-8 | 23-31-17 | SM00010 | | S | | SM00014 | | S | | 050-099 | |
| 211B | 22 | PB | L | 5-11 | 23-31-17 | SM00010 | | S | | SM00013 | | S | | 150-199, 275-278 | |
| 211B | 22 | PB | L | 7-1 | 23-31-17 | SM00010 | | S | | SM00014 | | S | | 280-299 | |
| 211R | 22 | PB | L | 0-0 | 23-31-17 | SM00009 | | S | | SM00013 | | S | | 050-099, 280-299 | |
| 211R | 22 | PB | L | 0-0 | 23-31-17 | SM00009 | | S | | SM00014 | | S | | 150-199, 275-278 | |
| 212B | 22 | PB | M | 1-11 | 23-31-17 | SM00014 | | S | | D03314 | 2 | | | 050-099 | |
| 212B | 22 | PB | M | 3-1 | 23-31-17 | SM00013 | | S | | D03314 | 2 | | | 150-199 | |
| 212B | 22 | PB | M | 2-9 | 23-31-17 | SM00013 | | S | | D03314 | 2 | | | 275-278 | |
| 212B | 22 | PB | M | 2-10 | 23-31-17 | SM00014 | | S | | D03314 | 2 | | | 280-299 | |
| 212R | 22 | PB | M | 0-0 | 23-31-17 | SM00013 | | S | | D03314 | 1 | | | 050-099, 280-299 | |
| 212R | 22 | PB | M | 0-0 | 23-31-17 | SM00014 | | S | | D03314 | 1 | | | 150-199, 275-278 | |
| 214B | 22 | PB | P | 2-11 | 23-31-17 | SM00014 | | S | | D03316 | 2 | | | 050-099 | |
| 214B | 22 | PB | P | 1-11 | 23-31-17 | SM00013 | | S | | D03316 | 2 | | | 150-199 | |
| 214B | 22 | PB | P | 2-2 | 23-31-17 | SM00013 | | S | | D03316 | 2 | | | 275-278 | |
| 214B | 22 | PB | P | 2-1 | 23-31-17 | SM00014 | | S | | D03316 | 2 | | | 280-299 | |
| 214R | 22 | PB | P | 0-0 | 23-31-17 | SM00013 | | S | | D03316 | 1 | | | 050-099, 280-299 | |
| 214R | 22 | PB | P | 0-0 | 23-31-17 | SM00014 | | S | | D03316 | 1 | | | 150-199, 275-278 | |
| 215B | 22 | PB | R | 6-1 | 23-31-17 | SM00014 | | S | | SM00018 | | S | | 050-099 | |
| 215B | 22 | PB | R | 4-10 | 23-31-17 | SM00013 | | S | | SM00017 | | S | | 150-199 | |
| 215B | 22 | PB | R | 5-1 | 23-31-17 | SM00013 | | S | | SM00017 | | S | | 275-278 | |
| 215B | 22 | PB | R | 4-10 | 23-31-17 | SM00014 | | S | | SM00018 | | S | | 280-299 | |
| 215R | 22 | PB | R | 0-0 | 23-31-17 | SM00013 | | S | | SM00017 | | S | | 050-099, 280-299 | |
| 215R | 22 | PB | R | 0-0 | 23-31-17 | SM00014 | | S | | SM00018 | | S | | 150-199, 275-278 | |
| 216B | 22 | PB | T | 1-11 | 23-31-17 | SM00018 | | S | | D03318 | 2 | | | 050-099 | |
| 216B | 22 | PB | T | 2-0 | 23-31-17 | SM00017 | | S | | D03318 | 2 | | | 150-199 | |
| 216B | 22 | PB | T | 2-1 | 23-31-17 | SM00017 | | S | | D03318 | 2 | | | 275-278 | |
| 216B | 22 | PB | T | 2-0 | 23-31-17 | SM00018 | | S | | D03318 | 2 | | | 280-299 | |
| 216R | 22 | PB | T | 0-0 | 23-31-17 | SM00017 | | S | | D03318 | 1 | | | 050-099, 280-299 | |
| 216R | 22 | PB | T | 0-0 | 23-31-17 | SM00018 | | S | | D03318 | 1 | | | 150-199, 275-278 | |
| 218B | 22 | PB | V | 2-9 | 23-31-17 | SM00018 | | S | | D03320 | 2 | | | 050-099 | |
| 218B | 22 | PB | V | 3-0 | 23-31-17 | SM00017 | | S | | D03320 | 2 | | | 150-199 | |
| 218B | 22 | PB | V | 2-11 | 23-31-17 | SM00017 | | S | | D03320 | 2 | | | 275-278 | |
| 218B | 22 | PB | V | 3-1 | 23-31-17 | SM00018 | | S | | D03320 | 2 | | | 280-299 | |
| 218R | 22 | PB | V | 0-0 | 23-31-17 | SM00017 | | S | | D03320 | 1 | | | 050-099, 280-299 | |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 23

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | | |
| 218R | 22 | PB | V | 0-0 | 23-31-17 | SM00018 | | | S | | D03320 | | 1 | | 150-199, 275-278 | |
| 219B | 22 | PB | W | 7-1 | 23-31-17 | SM00018 | | | S | | SM00022 | | | S | 050-099, 280-299 | |
| 219B | 22 | PB | W | 6-8 | 23-31-17 | SM00017 | | | S | | SM00164 | | | S | 150-199 | |
| 219B | 22 | PB | W | 6-11 | 23-31-17 | SM00017 | | | S | | SM00164 | | | S | 275-278 | |
| 219R | 22 | PB | W | 0-0 | 23-31-17 | SM00017 | | | S | | SM00021 | | | S | 050-099, 280-299 | |
| 219R | 22 | PB | W | 0-0 | 23-31-17 | SM00018 | | | S | | SM00165 | | | S | 150-199, 275-278 | |
| 220B | 22 | PB | X | 2-10 | 23-31-17 | SM00022 | | | S | | D03322 | | 2 | | 050-099 | |
| 220B | 22 | PB | X | 1-8 | 23-31-17 | SM00019 | | | S | | D03322 | | 2 | | 275-278 | |
| 220B | 22 | PB | X | 2-11 | 23-31-17 | SM00022 | | | S | | D08156 | | 2 | | 280-299 | |
| 220R | 22 | PB | X | 0-0 | 23-31-17 | SM00021 | | | S | | D03322 | | 1 | | 050-099 | |
| 220R | 22 | PB | X | 0-0 | 23-31-17 | SM00020 | | | S | | D03322 | | 1 | | 275-278 | |
| 220R | 22 | PB | X | 0-0 | 23-31-17 | SM00021 | | | S | | D08156 | | 1 | | 280-299 | |
| 221B | 22 | PB | Y | 4-6 | 23-31-17 | SM00019 | | | S | | D06516J | | 2 | | 150-199 | |
| 221B | 22 | PB | Y | 3-6 | 23-31-17 | SM00019 | | | S | | D06516J | | 2 | | 275-278 | |
| 221R | 22 | PB | Y | 0-0 | 23-31-17 | SM00020 | | | S | | D06516J | | 1 | | 150-199, 275-278 | |
| 222B | 22 | PB | AA | 1-7 | 23-31-17 | SM00022 | | | S | | D03324 | | 2 | | 050-099 | |
| 222B | 22 | PB | BM | 1-7 | 23-31-17 | SM00168 | | | S | | D03324 | | 2 | | 150-199 | |
| 222B | 22 | PB | IV | 1-7 | 23-31-17 | D08158 | | 2 | | | SM00022 | | | S | 280-299 | |
| 222R | 22 | PB | AA | 0-0 | 23-31-17 | SM00021 | | | S | | D03324 | | 1 | | 050-099 | |
| 222R | 22 | PB | BM | 0-0 | 23-31-17 | SM00169 | | | S | | D03324 | | 1 | | 150-199 | |
| 222R | 22 | PB | IV | 0-0 | 23-31-17 | D08158 | | 1 | | | SM00021 | | | S | 280-299 | |
| 223B | 22 | PB | AB | 5-11 | 23-31-17 | SM00022 | | | S | | SM00026 | | | S | 050-099 | |
| 223B | 22 | PB | IW | 24-10 | 23-31-17 | SM00026 | | | S | | SM00022 | | | S | 280-299 | |
| 223R | 22 | PB | AB | 0-0 | 23-31-17 | SM00021 | | | S | | SM00025 | | | S | 050-099 | |
| 223R | 22 | PB | IW | 0-0 | 23-31-17 | SM00025 | | | S | | SM00021 | | | S | 280-299 | |
| 224B | 22 | PB | AC | 3-1 | 23-31-17 | SM00026 | | | S | | D03326 | | 2 | | 050-099 | |
| 224B | 22 | PB | X | 2-6 | 23-31-17 | SM00019 | | | S | | D03326 | | 2 | | 150-199 | |
| 224B | 22 | PB | IX | 2-11 | 23-31-17 | D08160 | | 2 | | | SM00026 | | | S | 280-299 | |
| 224R | 22 | PB | AC | 0-0 | 23-31-17 | SM00025 | | | S | | D03326 | | 1 | | 050-099 | |
| 224R | 22 | PB | X | 0-0 | 23-31-17 | SM00020 | | | S | | D03326 | | 1 | | 150-199 | |
| 224R | 22 | PB | IX | 0-0 | 23-31-17 | D08160 | | 1 | | | SM00025 | | | S | 280-299 | |
| 226B | 22 | PB | AE | 1-8 | 23-31-17 | SM00026 | | | S | | D03328 | | 2 | | 050-099 | |
| 226B | 22 | PB | JA | 2-1 | 23-31-17 | D08162 | | 2 | | | SM00026 | | | S | 280-299 | |
| 226R | 22 | PB | AE | 0-0 | 23-31-17 | SM00025 | | | S | | D03328 | | 1 | | 050-099 | |
| 226R | 22 | PB | JA | 0-0 | 23-31-17 | D08162 | | 1 | | | SM00025 | | | S | 280-299 | |
| 227B | 22 | PB | JB | 4-11 | 23-31-17 | SM00030 | | | S | | SM00026 | | | S | 280-299 | |
| 227R | 22 | PB | JB | 0-0 | 23-31-17 | SM00029 | | | S | | SM00025 | | | S | 280-299 | |
| 228B | 22 | PB | AG | 4-2 | 23-31-17 | SM00026 | | | S | | D03330 | | 2 | | 050-099 | |
| 228B | 22 | PB | JC | 2-3 | 23-31-17 | D03322 | | 2 | | | SM00030 | | | S | 280-299 | |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 24

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | | |
| 228R | 22 | PB | AG | | 0-0 | 23-31-17 | SM00025 | | | S | | D03330 | 1 | | | 050-099 |
| 228R | 22 | PB | JC | | 0-0 | 23-31-17 | D03322 | | 1 | | | SM00029 | | S | | 280-299 |
| 231B | 22 | PB | JF | | 1-8 | 23-31-17 | SM00030 | | | S | | D06516J | 2 | | | 280-299 |
| 231R | 22 | PB | JF | | 0-0 | 23-31-17 | SM00029 | | | S | | D06516J | 1 | | | 280-299 |
| 234B | 22 | PB | AN | | 4-3 | 23-31-17 | SM00036 | | | S | | D03336 | 2 | | | 050-099 |
| 234R | 22 | PB | AN | | 0-0 | 23-31-17 | SM00035 | | | S | | D03336 | 1 | | | 050-099 |
| 236B | 22 | PB | AR | | 1-10 | 23-31-17 | SM00036 | | | S | | D03338 | 2 | | | 050-099 |
| 236R | 22 | PB | AR | | 0-0 | 23-31-17 | SM00035 | | | S | | D03338 | 1 | | | 050-099 |
| 237B | 22 | PB | AT | | 3-9 | 23-31-17 | SM00036 | | | S | | SM00040 | | S | | 050-099 |
| 237R | 22 | PB | AT | | 0-0 | 23-31-17 | SM00035 | | | S | | SM00039 | | S | | 050-099 |
| 238B | 22 | PB | AU | | 2-0 | 23-31-17 | SM00040 | | | S | | D03340 | 2 | | | 050-099 |
| 238R | 22 | PB | AU | | 0-0 | 23-31-17 | SM00039 | | | S | | D03340 | 1 | | | 050-099 |
| 240B | 22 | PB | AW | | 1-7 | 23-31-17 | SM00040 | | | S | | D03342 | 2 | | | 050-099 |
| 240R | 22 | PB | AW | | 0-0 | 23-31-17 | SM00039 | | | S | | D03342 | 1 | | | 050-099 |
| 241B | 22 | PB | AX | | 4-8 | 23-31-17 | SM00040 | | | S | | SM00044 | | S | | 050-099 |
| 241R | 22 | PB | AX | | 0-0 | 23-31-17 | SM00039 | | | S | | SM00043 | | S | | 050-099 |
| 242B | 22 | PB | AY | | 1-10 | 23-31-17 | SM00044 | | | S | | D03344 | 2 | | | 050-099 |
| 242R | 22 | PB | AY | | 0-0 | 23-31-17 | SM00043 | | | S | | D03344 | 1 | | | 050-099 |
| 244B | 22 | PB | BB | | 2-11 | 23-31-17 | SM00044 | | | S | | D03346 | 2 | | | 050-099 |
| 244R | 22 | PB | BB | | 0-0 | 23-31-17 | SM00043 | | | S | | D03346 | 1 | | | 050-099 |
| 245B | 22 | PB | BC | | 17-7 | 23-31-17 | SM00044 | | | S | | D05168P | 2 | | | 050-099 |
| 245R | 22 | PB | BC | | 0-0 | 23-31-17 | SM00043 | | | S | | D05168P | 1 | | | 050-099 |
| 246B | 22 | PB | BD | | 3-5 | 23-31-17 | D03202 | | 2 | | | SM00092 | | S | | 275-278 |
| 246B | 22 | PB | BD | | 2-9 | 23-31-17 | D03202 | | 2 | | | SM00002 | | S | | 280-299 |
| 246R | 22 | PB | BD | | 0-0 | 23-31-17 | D03202 | | 1 | | | SM00091 | | S | | 275-278 |
| 246R | 22 | PB | BD | | 0-0 | 23-31-17 | D03202 | | 1 | | | SM00001 | | S | | 280-299 |
| 248B | 22 | PB | BF | | 2-8 | 23-31-17 | SM00164 | | | S | | D08156 | 2 | | | 150-199 |
| 248B | 22 | PB | BF | | 2-11 | 23-31-17 | SM00164 | | | S | | D08156 | 2 | | | 275-278 |
| 248R | 22 | PB | BF | | 0-0 | 23-31-17 | SM00165 | | | S | | D08156 | 1 | | | 150-199, 275-278 |
| 251B | 22 | PB | CB | | 19-11 | 23-31-17 | D05166P | | 5 | | | SM00106 | | S | | 050-099 |
| 251B | 22 | PB | BA | | 19-2 | 23-31-17 | D05166P | | 5 | | | SM00161 | | S | | 150-157 |
| 251B | 22 | PB | BA | | 20-3 | 23-31-17 | D05166P | | 5 | | | SM00106 | | S | | 162-199 |
| 251R | 22 | PB | CB | | 0-0 | 23-31-17 | D05166P | | 6 | | | SM00105 | | S | | 050-099 |
| 251R | 22 | PB | BA | | 0-0 | 23-31-17 | D05166P | | 6 | | | SM00160 | | S | | 150-157 |
| 251R | 22 | PB | BA | | 0-0 | 23-31-17 | D05166P | | 6 | | | SM00105 | | S | | 162-199 |
| 252B | 22 | PB | BY | | 2-6 | 23-31-17 | D03304 | | 7 | | | SM00161 | | S | | 150-157 |
| 252R | 22 | PB | BY | | 0-0 | 23-31-17 | D03304 | | 6 | | | SM00160 | | S | | 150-157 |
| 253B | 22 | PB | BC | | 2-2 | 23-31-17 | SM00161 | | | S | | SM00106 | | S | | 150-157 |
| 253R | 22 | PB | BC | | 0-0 | 23-31-17 | SM00160 | | | S | | SM00105 | | S | | 150-157 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 25

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | |
| 254B | 22 | PB | DD | 1-6 | 23-31-17 | SM00106 | | S | | D03306 | 7 | | | 050-099 | |
| 254B | 22 | PB | BE | 1-11 | 23-31-17 | D03306 | | 7 | | SM00106 | | S | | 150-199 | |
| 254R | 22 | PB | DD | 0-0 | 23-31-17 | SM00105 | | S | | D03306 | 6 | | | 050-099 | |
| 254R | 22 | PB | BE | 0-0 | 23-31-17 | D03306 | | 6 | | SM00105 | | S | | 150-199 | |
| 256B | 22 | PB | DF | 2-8 | 23-31-17 | SM00106 | | S | | D03308 | 7 | | | 050-099 | |
| 256B | 22 | PB | BG | 1-7 | 23-31-17 | D03308 | | 7 | | SM00106 | | S | | 150-199 | |
| 256R | 22 | PB | DF | 0-0 | 23-31-17 | SM00105 | | S | | D03308 | 6 | | | 050-099 | |
| 256R | 22 | PB | BG | 0-0 | 23-31-17 | D03308 | | 6 | | SM00105 | | S | | 150-199 | |
| 257B | 22 | PB | DG | 6-2 | 23-31-17 | SM00106 | | S | | SM00110 | | S | | 050-099 | |
| 257B | 22 | PB | BZ | 5-10 | 23-31-17 | SM00106 | | S | | SM00110 | | S | | 150-199 | |
| 257R | 22 | PB | DG | 0-0 | 23-31-17 | SM00105 | | S | | SM00109 | | S | | 050-099 | |
| 257R | 22 | PB | BZ | 0-0 | 23-31-17 | SM00105 | | S | | SM00109 | | S | | 150-199 | |
| 258B | 22 | PB | DH | 1-11 | 23-31-17 | SM00110 | | S | | D03310 | 7 | | | 050-099 | |
| 258B | 22 | PB | CA | 3-0 | 23-31-17 | D03310 | | 7 | | SM00110 | | S | | 150-199 | |
| 258R | 22 | PB | DH | 0-0 | 23-31-17 | SM00109 | | S | | D03310 | 6 | | | 050-099 | |
| 258R | 22 | PB | CA | 0-0 | 23-31-17 | D03310 | | 6 | | SM00109 | | S | | 150-199 | |
| 260B | 22 | PB | DJ | 2-7 | 23-31-17 | SM00110 | | S | | D03312 | 7 | | | 050-099 | |
| 260B | 22 | PB | BJ | 1-9 | 23-31-17 | D03312 | | 7 | | SM00110 | | S | | 150-199 | |
| 260R | 22 | PB | DJ | 0-0 | 23-31-17 | SM00109 | | S | | D03312 | 6 | | | 050-099 | |
| 260R | 22 | PB | BJ | 0-0 | 23-31-17 | D03312 | | 6 | | SM00109 | | S | | 150-199 | |
| 261B | 22 | PB | DK | 5-8 | 23-31-17 | SM00110 | | S | | SM00114 | | S | | 050-099 | |
| 261B | 22 | PB | CB | 5-11 | 23-31-17 | SM00110 | | S | | SM00113 | | S | | 150-199 | |
| 261R | 22 | PB | DK | 0-0 | 23-31-17 | SM00109 | | S | | SM00113 | | S | | 050-099 | |
| 261R | 22 | PB | CB | 0-0 | 23-31-17 | SM00109 | | S | | SM00114 | | S | | 150-199 | |
| 262B | 22 | PB | DL | 1-11 | 23-31-17 | SM00114 | | S | | D03314 | 7 | | | 050-099 | |
| 262B | 22 | PB | CC | 3-1 | 23-31-17 | D03314 | | 7 | | SM00113 | | S | | 150-199 | |
| 262R | 22 | PB | DL | 0-0 | 23-31-17 | SM00113 | | S | | D03314 | 6 | | | 050-099 | |
| 262R | 22 | PB | CC | 0-0 | 23-31-17 | D03314 | | 6 | | SM00114 | | S | | 150-199 | |
| 264B | 22 | PB | DN | 2-11 | 23-31-17 | SM00114 | | S | | D03316 | 7 | | | 050-099 | |
| 264B | 22 | PB | CD | 1-11 | 23-31-17 | D03316 | | 7 | | SM00113 | | S | | 150-199 | |
| 264R | 22 | PB | DN | 0-0 | 23-31-17 | SM00113 | | S | | D03316 | 6 | | | 050-099 | |
| 264R | 22 | PB | CD | 0-0 | 23-31-17 | D03316 | | 6 | | SM00114 | | S | | 150-199 | |
| 265B | 22 | PB | DO | 6-1 | 23-31-17 | SM00114 | | S | | SM00118 | | S | | 050-099 | |
| 265B | 22 | PB | CE | 4-10 | 23-31-17 | SM00113 | | S | | SM00117 | | S | | 150-199 | |
| 265R | 22 | PB | DO | 0-0 | 23-31-17 | SM00113 | | S | | SM00117 | | S | | 050-099 | |
| 265R | 22 | PB | CE | 0-0 | 23-31-17 | SM00114 | | S | | SM00118 | | S | | 150-199 | |
| 266B | 22 | PB | DP | 1-11 | 23-31-17 | SM00118 | | S | | D03318 | 7 | | | 050-099 | |
| 266B | 22 | PB | BN | 2-0 | 23-31-17 | D03318 | | 7 | | SM00117 | | S | | 150-199 | |
| 266R | 22 | PB | DP | 0-0 | 23-31-17 | SM00117 | | S | | D03318 | 6 | | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 26

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | | |
| 266R | 22 | PB | BN | | 0-0 | 23-31-17 | D03318 | | 6 | | | SM00118 | | S | | 150-199 |
| 268B | 22 | PB | DR | | 2-9 | 23-31-17 | SM00118 | | | S | | D03320 | 7 | | | 050-099 |
| 268B | 22 | PB | BO | | 3-0 | 23-31-17 | D03320 | | 7 | | | SM00117 | | S | | 150-199 |
| 268R | 22 | PB | DR | | 0-0 | 23-31-17 | SM00117 | | | S | | D03320 | 6 | | | 050-099 |
| 268R | 22 | PB | BO | | 0-0 | 23-31-17 | D03320 | | 6 | | | SM00118 | | S | | 150-199 |
| 269B | 22 | PB | DS | | 7-1 | 23-31-17 | SM00118 | | | S | | SM00122 | | S | | 050-099 |
| 269B | 22 | PB | BX | | 4-6 | 23-31-17 | SM00119 | | | S | | D06516J | 6 | | | 150-199 |
| 269R | 22 | PB | DS | | 0-0 | 23-31-17 | SM00117 | | | S | | SM00121 | | S | | 050-099 |
| 269R | 22 | PB | BX | | 0-0 | 23-31-17 | SM00120 | | | S | | D06516J | 5 | | | 150-199 |
| 270B | 22 | PB | DT | | 2-10 | 23-31-17 | SM00122 | | | S | | D03322 | 7 | | | 050-099 |
| 270R | 22 | PB | DT | | 0-0 | 23-31-17 | SM00121 | | | S | | D03322 | 6 | | | 050-099 |
| 272B | 22 | PB | CC | | 1-7 | 23-31-17 | SM00122 | | | S | | D03324 | 7 | | | 050-099 |
| 272R | 22 | PB | CC | | 0-0 | 23-31-17 | SM00121 | | | S | | D03324 | 6 | | | 050-099 |
| 273B | 22 | PB | CD | | 5-11 | 23-31-17 | SM00122 | | | S | | SM00126 | | S | | 050-099 |
| 273R | 22 | PB | CD | | 0-0 | 23-31-17 | SM00121 | | | S | | SM00125 | | S | | 050-099 |
| 274B | 22 | PB | CE | | 3-1 | 23-31-17 | SM00126 | | | S | | D03326 | 7 | | | 050-099 |
| 274B | 22 | PB | BW | | 2-6 | 23-31-17 | D03326 | | 7 | | | SM00119 | | S | | 150-199 |
| 274R | 22 | PB | CE | | 0-0 | 23-31-17 | SM00125 | | | S | | D03326 | 6 | | | 050-099 |
| 274R | 22 | PB | BW | | 0-0 | 23-31-17 | D03326 | | 6 | | | SM00120 | | S | | 150-199 |
| 276B | 22 | PB | CG | | 1-8 | 23-31-17 | SM00126 | | | S | | D03328 | 7 | | | 050-099 |
| 276R | 22 | PB | CG | | 0-0 | 23-31-17 | SM00125 | | | S | | D03328 | 6 | | | 050-099 |
| 277B | 22 | PB | CH | | 2-2 | 23-31-17 | SM00126 | | | S | | SM00130 | | S | | 050-099 |
| 277R | 22 | PB | CH | | 0-0 | 23-31-17 | SM00125 | | | S | | SM00129 | | S | | 050-099 |
| 278B | 22 | PB | CA | | 3-0 | 23-31-17 | SM00130 | | | S | | D03330 | 7 | | | 050-099 |
| 278R | 22 | PB | CA | | 0-0 | 23-31-17 | SM00129 | | | S | | D03330 | 6 | | | 050-099 |
| 279B | 22 | PB | CI | | 22-7 | 23-31-17 | SM00136 | | | S | | SM00130 | | S | | 050-099 |
| 279R | 22 | PB | CI | | 0-0 | 23-31-17 | SM00135 | | | S | | SM00129 | | S | | 050-099 |
| 284B | 22 | PB | CN | | 4-3 | 23-31-17 | SM00136 | | | S | | D03336 | 7 | | | 050-099 |
| 284R | 22 | PB | CN | | 0-0 | 23-31-17 | SM00135 | | | S | | D03336 | 6 | | | 050-099 |
| 286B | 22 | PB | CP | | 1-10 | 23-31-17 | SM00136 | | | S | | D03338 | 7 | | | 050-099 |
| 286R | 22 | PB | CP | | 0-0 | 23-31-17 | SM00135 | | | S | | D03338 | 6 | | | 050-099 |
| 287B | 22 | PB | CQ | | 3-9 | 23-31-17 | SM00136 | | | S | | SM00140 | | S | | 050-099 |
| 287R | 22 | PB | CQ | | 0-0 | 23-31-17 | SM00135 | | | S | | SM00139 | | S | | 050-099 |
| 288B | 22 | PB | CR | | 2-0 | 23-31-17 | SM00140 | | | S | | D03340 | 7 | | | 050-099 |
| 288R | 22 | PB | CR | | 0-0 | 23-31-17 | SM00139 | | | S | | D03340 | 6 | | | 050-099 |
| 290B | 22 | PB | CT | | 1-7 | 23-31-17 | SM00140 | | | S | | D03342 | 7 | | | 050-099 |
| 290R | 22 | PB | CT | | 0-0 | 23-31-17 | SM00139 | | | S | | D03342 | 6 | | | 050-099 |
| 291B | 22 | PB | CU | | 4-8 | 23-31-17 | SM00140 | | | S | | SM00144 | | S | | 050-099 |
| 291R | 22 | PB | CU | | 0-0 | 23-31-17 | SM00139 | | | S | | SM00143 | | S | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 27

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|-------|------|------|---------|-------------|--|---|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | | | | | |
| 292B | 22 | PB | CV | | 1-10 | 23-31-17 | SM00144 | | | | S | | | | D03344 | 7 | | | 050-099 |
| 292R | 22 | PB | CV | | 0-0 | 23-31-17 | SM00143 | | | | S | | | | D03344 | 6 | | | 050-099 |
| 294B | 22 | PB | CY | | 2-11 | 23-31-17 | SM00144 | | | | S | | | | D03346 | 7 | | | 050-099 |
| 294R | 22 | PB | CY | | 0-0 | 23-31-17 | SM00143 | | | | S | | | | D03346 | 6 | | | 050-099 |
| 295B | 22 | PB | CZ | | 17-7 | 23-31-17 | SM00144 | | | | S | | | | D05168P | 5 | | | 050-099 |
| 295R | 22 | PB | CZ | | 0-0 | 23-31-17 | SM00143 | | | | S | | | | D05168P | 6 | | | 050-099 |
| 296B | 22 | PB | BP | | 6-8 | 23-31-17 | SM00117 | | | | S | | | | SM00264 | | | S | 150-199 |
| 296R | 22 | PB | BP | | 0-0 | 23-31-17 | SM00118 | | | | S | | | | SM00265 | | | S | 150-199 |
| 298B | 22 | PB | BH | | 2-1 | 23-31-17 | SM00164 | | | | S | | | | D08158 | 2 | | | 150-199 |
| 298B | 22 | PB | BH | | 2-0 | 23-31-17 | SM00164 | | | | S | | | | D08158 | 2 | | | 275-278 |
| 298R | 22 | PB | BH | | 0-0 | 23-31-17 | SM00165 | | | | S | | | | D08158 | 1 | | | 150-199, 275-278 |
| 299B | 22 | PB | BI | | 20-8 | 23-31-17 | SM00164 | | | | S | | | | SM00168 | | | S | 150-199 |
| 299B | 22 | PB | BI | | 5-6 | 23-31-17 | SM00164 | | | | S | | | | SM00168 | | | S | 275-278 |
| 299R | 22 | PB | BI | | 0-0 | 23-31-17 | SM00165 | | | | S | | | | SM00169 | | | S | 150-199, 275-278 |
| 537 | 18 | PA | | | 20-8 | 33-24-14 | SM00147 | | | | S | | | | SM00151 | | | S | 150-199 |
| 537 | 18 | PA | | | 5-6 | 33-24-14 | SM00147 | | | | S | | | | SM00151 | | | S | 275-278 |
| 537 | 18 | PA | | | 24-10 | 33-24-14 | SM00147 | | | | S | | | | SM00151 | | | S | 280-299 |
| 538 | 18 | PA | | | 20-8 | 33-24-14 | SM00148 | | | | S | | | | SM00152 | | | S | 150-199 |
| 538 | 18 | PA | | | 5-6 | 33-24-14 | SM00148 | | | | S | | | | SM00152 | | | S | 275-278 |
| 538 | 18 | PA | | | 24-10 | 33-24-14 | SM00148 | | | | S | | | | SM00152 | | | S | 280-299 |
| 541 | 18 | PA | | | 3-2 | 33-24-14 | SM00151 | | | | S | | | | SM00065 | | | S | 150-154, 162-163 |
| 541 | 18 | PA | | | 3-6 | 33-24-14 | SM00151 | | | | S | | | | SM00063 | | | S | 275-278 |
| 541 | 18 | PA | | | 4-11 | 33-24-14 | SM00151 | | | | S | | | | SM00063 | | | S | 280-299 |
| 542 | 18 | PA | | | 3-2 | 33-24-14 | SM00152 | | | | S | | | | SM00066 | | | S | 150-154, 162-163 |
| 542 | 18 | PA | | | 3-6 | 33-24-14 | SM00152 | | | | S | | | | SM00064 | | | S | 275-278 |
| 542 | 18 | PA | | | 4-11 | 33-24-14 | SM00152 | | | | S | | | | SM00064 | | | S | 280-299 |
| 543 | 20 | PA | | | 2-8 | 33-24-14 | SM00147 | | | | S | | | | D08156 | 4 | | | 150-199 |
| 543 | 20 | PA | | | 2-11 | 33-24-14 | SM00147 | | | | S | | | | D08156 | 4 | | | 275-299 |
| 544 | 20 | PA | | | 2-8 | 33-24-14 | SM00148 | | | | S | | | | D08156 | 3 | | | 150-199 |
| 544 | 20 | PA | | | 2-11 | 33-24-14 | SM00148 | | | | S | | | | D08156 | 3 | | | 275-299 |
| 545 | 20 | PA | | | 1-11 | 33-24-14 | GD05036 | | | A.. | E | | | | D08156 | 5 | | | 150-199 |
| 545 | 20 | PA | | | 1-10 | 33-24-14 | GD05036 | | | A.. | E | | | | D08156 | 5 | | | 275-278 |
| 545 | 20 | PA | | | 17-6 | 33-24-14 | GD01592 | | | A.. | E | | | | D08156 | 5 | | | 280-299 |
| 546 | 20 | PA | | | 2-1 | 33-24-14 | SM00147 | | | | S | | | | D08158 | 4 | | | 150-199 |
| 546 | 20 | PA | | | 2-0 | 33-24-14 | SM00147 | | | | S | | | | D08158 | 4 | | | 275-278 |
| 546 | 20 | PA | | | 1-7 | 33-24-14 | SM00147 | | | | S | | | | D08158 | 4 | | | 280-299 |
| 547 | 20 | PA | | | 2-1 | 33-24-14 | SM00148 | | | | S | | | | D08158 | 3 | | | 150-199 |
| 547 | 20 | PA | | | 2-0 | 33-24-14 | SM00148 | | | | S | | | | D08158 | 3 | | | 275-278 |
| 547 | 20 | PA | | | 1-7 | 33-24-14 | SM00148 | | | | S | | | | D08158 | 3 | | | 280-299 |

WIRE LIST

D280T132

91-21-11
 Section W0800
 Page 28
 Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|---------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0804 | 286T0804 | | | SPEAKERS AND PASS. SIGNS,MID RIGHT (continued) | | | | | | | | | | | |
| 548 | 20 | PA | | | 3-11 | 33-24-14 | GD05036 | | A.. | E | | D08158 | 5 | | 150-199 |
| 548 | 20 | PA | | | 4-1 | 33-24-14 | GD05036 | | A.. | E | | D08158 | 5 | | 275-278 |
| 548 | 20 | PA | | | 19-7 | 33-24-14 | GD01592 | | A.. | E | | D08158 | 5 | | 280-299 |
| 549 | 20 | PA | | | 16-10 | 33-24-14 | SM00151 | | | S | | D08160 | 4 | | 150-199 |
| 549 | 20 | PA | | | 2-8 | 33-24-14 | SM00151 | | | S | | D08160 | 4 | | 275-278 |
| 549 | 20 | PA | | | 2-11 | 33-24-14 | SM00151 | | | S | | D08160 | 4 | | 280-299 |
| 550 | 20 | PA | | | 16-10 | 33-24-14 | SM00152 | | | S | | D08160 | 3 | | 150-199 |
| 550 | 20 | PA | | | 2-8 | 33-24-14 | SM00152 | | | S | | D08160 | 3 | | 275-278 |
| 550 | 20 | PA | | | 2-11 | 33-24-14 | SM00152 | | | S | | D08160 | 3 | | 280-299 |
| 551 | 20 | PA | | | 2-1 | 33-24-14 | GD05632 | | A.. | E | | D08160 | 5 | | 150-199 |
| 551 | 20 | PA | | | 4-6 | 33-24-14 | GD05040 | | A.. | E | | D08160 | 5 | | 275-278 |
| 551 | 20 | PA | | | 4-3 | 33-24-14 | GD05040 | | A.. | E | | D08160 | 5 | | 280-299 |
| 552 | 20 | PA | | | 2-4 | 33-24-14 | SM00151 | | | S | | D08162 | 4 | | 275-278 |
| 552 | 20 | PA | | | 2-1 | 33-24-14 | SM00151 | | | S | | D08162 | 4 | | 280-299 |
| 553 | 20 | PA | | | 2-4 | 33-24-14 | SM00152 | | | S | | D08162 | 3 | | 275-278 |
| 553 | 20 | PA | | | 2-1 | 33-24-14 | SM00152 | | | S | | D08162 | 3 | | 280-299 |
| 554 | 20 | PA | | | 1-11 | 33-24-14 | GD05040 | | A.. | E | | D08162 | 5 | | 275-278 |
| 554 | 20 | PA | | | 1-9 | 33-24-14 | GD05040 | | A.. | E | | D08162 | 5 | | 280-299 |
| 577B | 22 | PB | BQ | | 2-8 | 23-31-17 | D08156 | | | 7 | | SM00264 | | S | 150-199 |
| 577R | 22 | PB | BQ | | 0-0 | 23-31-17 | D08156 | | | 6 | | SM00265 | | S | 150-199 |
| 578B | 22 | PB | BR | | 2-1 | 23-31-17 | D08158 | | | 7 | | SM00264 | | S | 150-199 |
| 578R | 22 | PB | BR | | 0-0 | 23-31-17 | D08158 | | | 6 | | SM00265 | | S | 150-199 |
| 579B | 22 | PB | BS | | 20-8 | 23-31-17 | SM00264 | | | S | | SM00268 | | S | 150-199 |
| 579R | 22 | PB | BS | | 0-0 | 23-31-17 | SM00265 | | | S | | SM00269 | | S | 150-199 |
| 580B | 22 | PB | BT | | 16-10 | 23-31-17 | D08160 | | | 7 | | SM00268 | | S | 150-199 |
| 580R | 22 | PB | BT | | 0-0 | 23-31-17 | D08160 | | | 6 | | SM00269 | | S | 150-199 |
| 582B | 22 | PB | BV | | 3-2 | 23-31-17 | SM00268 | | | S | | SM00119 | | S | 150-199 |
| 582R | 22 | PB | BV | | 0-0 | 23-31-17 | SM00269 | | | S | | SM00120 | | S | 150-199 |
| 602B | 22 | PB | BK | | 16-10 | 23-31-17 | SM00168 | | | S | | D08160 | 2 | | 150-199 |
| 602B | 22 | PB | BK | | 2-8 | 23-31-17 | SM00168 | | | S | | D08160 | 2 | | 275-278 |
| 602R | 22 | PB | BK | | 0-0 | 23-31-17 | SM00169 | | | S | | D08160 | 1 | | 150-199, 275-278 |
| 603B | 22 | PB | BL | | 3-2 | 23-31-17 | SM00168 | | | S | | SM00019 | | S | 150-199 |
| 603B | 22 | PB | BL | | 3-6 | 23-31-17 | SM00168 | | | S | | SM00019 | | S | 275-278 |
| 603R | 22 | PB | BL | | 0-0 | 23-31-17 | SM00169 | | | S | | SM00020 | | S | 150-199, 275-278 |
| 604B | 22 | PB | BM | | 2-4 | 23-31-17 | SM00168 | | | S | | D08162 | 2 | | 275-278 |
| 604R | 22 | PB | BM | | 0-0 | 23-31-17 | SM00169 | | | S | | D08162 | 1 | | 275-278 |
| 652B | 22 | PB | BU | | 1-7 | 23-31-17 | D03324 | | | 7 | | SM00268 | | S | 150-199 |
| 652R | 22 | PB | BU | | 0-0 | 23-31-17 | D03324 | | | 6 | | SM00269 | | S | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 29

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0805 | 286T0805 | | | WX RADAR TO PRESS. BLKHD | | | | | | | | | | | |
| 004 | 20 | | PA | | 5-0 | 34-43-22 | D00489 | | I- | | D04919P | 24 | | | ALL |
| 005 | 20 | | PA | | 5-0 | 34-43-22 | D00489 | | Z- | | D04919P | 25 | | | ALL |
| 006 | 20 | | PA | | 5-0 | 34-43-22 | D00489 | | N- | | D04919P | 22 | | | ALL |
| 007 | 20 | | PA | | 5-0 | 34-43-22 | D00489 | | HH | | D04919P | 1 | | | ALL |
| 201B | 20 | | PR | IA | 5-0 | 34-43-22 | D00489 | | T- | | D04919P | 18 | | | ALL |
| 201R | 20 | | PR | IA | 0-0 | 34-43-22 | D00489 | | S- | | D04919P | 17 | | | ALL |
| 201Z | | | | IA | 0-0 | 34-43-22 | D00489 | | DD | | D04919P | DED | | | ALL |
| 202B | 20 | | PR | IB | 5-0 | 34-43-22 | D00489 | | Q- | | D04919P | 20 | | | ALL |
| 202R | 20 | | PR | IB | 0-0 | 34-43-22 | D00489 | | P- | | D04919P | 19 | | | ALL |
| 202Z | | | | IB | 0-0 | 34-43-22 | D00489 | | BB | | D04919P | DED | | | ALL |
| 203B | 20 | | PR | IC | 5-0 | 34-43-22 | D00489 | | V- | | D04919P | 14 | | | ALL |
| 203R | 20 | | PR | IC | 0-0 | 34-43-22 | D00489 | | U- | | D04919P | 13 | | | ALL |
| 203Z | | | | IC | 0-0 | 34-43-22 | D00489 | | EE | | D04919P | DED | | | ALL |
| 204B | 20 | | PR | ID | 5-0 | 34-43-22 | D00489 | | Y | | D04919P | 45 | | | ALL |
| 204R | 20 | | PR | ID | 0-0 | 34-43-22 | D00489 | | X | | D04919P | 44 | | | ALL |
| 204Z | | | | ID | 0-0 | 34-43-22 | D00489 | | R- | | D04919P | DED | | | ALL |
| 205B | 20 | | PR | IE | 5-0 | 34-43-22 | D00489 | | F- | | D04919P | 16 | | | ALL |
| 205R | 20 | | PR | IE | 0-0 | 34-43-22 | D00489 | | E- | | D04919P | 15 | | | ALL |
| 205Z | | | | IE | 0-0 | 34-43-22 | D00489 | | W- | | D04919P | DED | | | ALL |
| 301B | 20 | | PS | MA | 5-0 | 34-43-22 | D00489 | | E | | D04919P | 53 | | | ALL |
| 301R | 20 | | PS | MA | 0-0 | 34-43-22 | D00489 | | D | | D04919P | 52 | | | ALL |
| 301Y | 20 | | PS | MA | 0-0 | 34-43-22 | D00489 | | F | | D04919P | 54 | | | ALL |
| 301Z | | | | MA | 0-0 | 34-43-22 | D00489 | | A- | | D04919P | DED | | | ALL |
| 302B | 20 | | PS | MB | 5-0 | 34-43-22 | D00489 | | B | | D04919P | 39 | | | ALL |
| 302R | 20 | | PS | MB | 0-0 | 34-43-22 | D00489 | | A | | D04919P | 40 | | | ALL |
| 302Y | 20 | | PS | MB | 0-0 | 34-43-22 | D00489 | | C | | D04919P | 38 | | | ALL |
| 302Z | | | | MB | 0-0 | 34-43-22 | D00489 | | W | | D04919P | DED | | | ALL |
| 303B | 20 | | PS | MC | 5-0 | 34-43-22 | D00489 | | H | | D04919P | 42 | | | ALL |
| 303R | 20 | | PS | MC | 0-0 | 34-43-22 | D00489 | | G | | D04919P | 41 | | | ALL |
| 303Y | 20 | | PS | MC | 0-0 | 34-43-22 | D00489 | | J | | D04919P | 43 | | | ALL |
| 303Z | | | | MC | 0-0 | 34-43-22 | D00489 | | D- | | D04919P | DED | | | ALL |
| YAA | | | | | 5-0 | 34-43-22 | D00489 | | REF | | D04919P | REF | | | ALL |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT | | | | | | | | | | | |
| 001 | 18 | | PA | | 13-10 | 33-24-12 | D05104P | 4 | | | SM00035 | | S | | 050-099 |
| 002 | 18 | | PA | | 13-10 | 33-24-12 | D05104P | 7 | | | SM00036 | | S | | 050-099 |
| 013 | 22 | | PA | | 1-8 | 33-24-12 | SM00036 | | | S | D03352 | 3 | | | 050-099 |
| 014 | 22 | | PA | | 1-8 | 33-24-12 | SM00035 | | | S | D03352 | 4 | | | 050-099 |
| 015 | 20 | | PA | | 4-7 | 33-24-12 | GD02788 | | A.. | E | D03352 | 5 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 30

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|---|--|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | | | | | |
| 016 | 18 | | PA | 4-1 | 33-24-12 | SM00035 | | | | | | | | S | SM00039 | | | | 050-099 |
| 017 | 18 | | PA | 4-1 | 33-24-12 | SM00036 | | | | | | | | S | SM00040 | | | | 050-099 |
| 018 | 22 | | PA | 3-3 | 33-24-12 | SM00040 | | | | | | | | S | D03354 | 3 | | | 050-099 |
| 019 | 22 | | PA | 3-3 | 33-24-12 | SM00039 | | | | | | | | S | D03354 | 4 | | | 050-099 |
| 020 | 20 | | PA | 4-4 | 33-24-12 | GD02152 | | A.. | E | | | | | | D03354 | 5 | | | 050-099 |
| 023 | 22 | | PA | 1-7 | 33-24-12 | SM00040 | | | | | | | | S | D03356 | 3 | | | 050-099 |
| 024 | 22 | | PA | 1-7 | 33-24-12 | SM00039 | | | | | | | | S | D03356 | 4 | | | 050-099 |
| 025 | 20 | | PA | 1-9 | 33-24-12 | GD02152 | | A.. | E | | | | | | D03356 | 5 | | | 050-099 |
| 026 | 18 | | PA | 4-11 | 33-24-12 | SM00039 | | | | | | | | S | SM00043 | | | | 050-099 |
| 027 | 18 | | PA | 4-11 | 33-24-12 | SM00040 | | | | | | | | S | SM00044 | | | | 050-099 |
| 028 | 22 | | PA | 2-3 | 33-24-12 | SM00044 | | | | | | | | S | D03358 | 3 | | | 050-099 |
| 029 | 22 | | PA | 2-3 | 33-24-12 | SM00043 | | | | | | | | S | D03358 | 4 | | | 050-099 |
| 030 | 20 | | PA | 4-2 | 33-24-12 | GD02152 | | A.. | E | | | | | | D03358 | 5 | | | 050-099 |
| 033 | 22 | | PA | 2-7 | 33-24-12 | SM00044 | | | | | | | | S | D03360 | 3 | | | 050-099 |
| 034 | 22 | | PA | 2-7 | 33-24-12 | SM00043 | | | | | | | | S | D03360 | 4 | | | 050-099 |
| 035 | 20 | | PA | 4-5 | 33-24-12 | GD02158 | | A.. | E | | | | | | D03360 | 5 | | | 050-099 |
| 036 | 18 | | PA | 5-10 | 33-24-12 | SM00043 | | | | | | | | S | SM00047 | | | | 050-099 |
| 037 | 18 | | PA | 5-10 | 33-24-12 | SM00044 | | | | | | | | S | SM00048 | | | | 050-099 |
| 038 | 22 | | PA | 1-10 | 33-24-12 | SM00048 | | | | | | | | S | D03362 | 3 | | | 050-099 |
| 039 | 22 | | PA | 1-10 | 33-24-12 | SM00047 | | | | | | | | S | D03362 | 4 | | | 050-099 |
| 040 | 20 | | PA | 1-9 | 33-24-12 | GD02158 | | A.. | E | | | | | | D03362 | 5 | | | 050-099 |
| 043 | 22 | | PA | 2-11 | 33-24-12 | SM00048 | | | | | | | | S | D03364 | 3 | | | 050-099 |
| 044 | 22 | | PA | 2-11 | 33-24-12 | SM00047 | | | | | | | | S | D03364 | 4 | | | 050-099 |
| 045 | 20 | | PA | 4-2 | 33-24-12 | GD02158 | | A.. | E | | | | | | D03364 | 5 | | | 050-099 |
| 046 | 18 | | PA | 5-10 | 33-24-12 | SM00047 | | | | | | | | S | SM00051 | | | | 050-099 |
| 047 | 18 | | PA | 5-10 | 33-24-12 | SM00048 | | | | | | | | S | SM00052 | | | | 050-099 |
| 048 | 22 | | PA | 1-11 | 33-24-12 | SM00052 | | | | | | | | S | D03366 | 3 | | | 050-099 |
| 049 | 22 | | PA | 1-11 | 33-24-12 | SM00051 | | | | | | | | S | D03366 | 4 | | | 050-099 |
| 050 | 20 | | PA | 4-1 | 33-24-12 | GD02164 | | A.. | E | | | | | | D03366 | 5 | | | 050-099 |
| 051 | 18 | | PA | 2-2 | 33-24-12 | D06514P | | | 4 | DL | | | | | SM00093 | | | | 150-199 |
| 051 | 18 | | PA | 3-0 | 33-24-12 | D06514P | | | 4 | DL | | | | | SM00067 | | | | 275-278 |
| 051 | 18 | | PA | 2-11 | 33-24-12 | D06514P | | | 4 | DL | | | | | SM00067 | | | | 280-299 |
| 052 | 18 | | PA | 2-2 | 33-24-12 | D06514P | | | 3 | DL | | | | | SM00094 | | | | 150-199 |
| 052 | 18 | | PA | 3-0 | 33-24-12 | D06514P | | | 3 | DL | | | | | SM00068 | | | | 275-278 |
| 052 | 18 | | PA | 2-11 | 33-24-12 | D06514P | | | 3 | DL | | | | | SM00068 | | | | 280-299 |
| 053 | 22 | | PA | 3-2 | 33-24-12 | SM00052 | | | | | | | | S | D03368 | 3 | | | 050-099 |
| 053 | 20 | | PA | 2-5 | 33-24-12 | SM00068 | | | | | | | | S | D03226 | 3 | | | 275-278 |
| 053 | 20 | | PA | 2-11 | 33-24-12 | SM00068 | | | | | | | | S | D03226 | 3 | | | 280-299 |
| 054 | 22 | | PA | 3-2 | 33-24-12 | SM00051 | | | | | | | | S | D03368 | 4 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 31

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | |
| 054 | 20 | | PA | | 2-5 | 33-24-12 | SM00067 | | S | | D03226 | | 4 | | 275-278 |
| 054 | 20 | | PA | | 2-11 | 33-24-12 | SM00067 | | S | | D03226 | | 4 | | 280-299 |
| 055 | 20 | | PA | | 1-10 | 33-24-12 | GD02164 | A.. | E | | D03368 | | 5 | | 050-099 |
| 055 | 20 | | PA | | 4-5 | 33-24-12 | GD05004 | A.. | E | | D03226 | | 5 | | 275-278 |
| 055 | 20 | | PA | | 6-0 | 33-24-12 | GD05004 | A.. | E | | D03226 | | 5 | | 280-299 |
| 056 | 18 | | PA | | 6-4 | 33-24-12 | SM00051 | | S | | SM00055 | | | S | 050-099 |
| 057 | 18 | | PA | | 6-4 | 33-24-12 | SM00052 | | S | | SM00056 | | | S | 050-099 |
| 058 | 22 | | PA | | 2-5 | 33-24-12 | SM00056 | | S | | D03370 | | 3 | | 050-099 |
| 058 | 20 | | PA | | 2-6 | 33-24-12 | SM00068 | | S | | D03228 | | 3 | | 275-278 |
| 058 | 20 | | PA | | 2-4 | 33-24-12 | SM00068 | | S | | D03228 | | 3 | | 280-299 |
| 059 | 22 | | PA | | 2-5 | 33-24-12 | SM00055 | | S | | D03370 | | 4 | | 050-099 |
| 059 | 20 | | PA | | 2-6 | 33-24-12 | SM00067 | | S | | D03228 | | 4 | | 275-278 |
| 059 | 20 | | PA | | 2-4 | 33-24-12 | SM00067 | | S | | D03228 | | 4 | | 280-299 |
| 060 | 20 | | PA | | 3-10 | 33-24-12 | GD02164 | A.. | E | | D03370 | | 5 | | 050-099 |
| 060 | 20 | | PA | | 1-11 | 33-24-12 | GD05004 | A.. | E | | D03228 | | 5 | | 275-278 |
| 060 | 20 | | PA | | 2-9 | 33-24-12 | GD05004 | A.. | E | | D03228 | | 5 | | 280-299 |
| 061 | 18 | | PA | | 5-5 | 33-24-12 | SM00067 | | S | | SM00093 | | | S | 275-278 |
| 061 | 18 | | PA | | 6-0 | 33-24-12 | SM00067 | | S | | SM00093 | | | S | 280-299 |
| 062 | 18 | | PA | | 5-5 | 33-24-12 | SM00068 | | S | | SM00094 | | | S | 275-278 |
| 062 | 18 | | PA | | 6-0 | 33-24-12 | SM00068 | | S | | SM00094 | | | S | 280-299 |
| 063 | 22 | | PA | | 2-4 | 33-24-12 | SM00056 | | S | | D03372 | | 3 | | 050-099 |
| 063 | 20 | | PA | | 2-1 | 33-24-12 | SM00094 | | S | | D03230 | | 3 | | 275-278 |
| 063 | 20 | | PA | | 2-3 | 33-24-12 | SM00094 | | S | | D03230 | | 3 | | 280-299 |
| 064 | 22 | | PA | | 2-4 | 33-24-12 | SM00055 | | S | | D03372 | | 4 | | 050-099 |
| 064 | 20 | | PA | | 2-1 | 33-24-12 | SM00093 | | S | | D03230 | | 4 | | 275-278 |
| 064 | 20 | | PA | | 2-3 | 33-24-12 | SM00093 | | S | | D03230 | | 4 | | 280-299 |
| 065 | 20 | | PA | | 4-3 | 33-24-12 | GD02170 | A.. | E | | D03372 | | 5 | | 050-099 |
| 065 | 20 | | PA | | 4-0 | 33-24-12 | GD05004 | A.. | E | | D03230 | | 5 | | 275-278 |
| 065 | 20 | | PA | | 3-5 | 33-24-12 | GD05004 | A.. | E | | D03230 | | 5 | | 280-299 |
| 066 | 18 | | PA | | 4-5 | 33-24-12 | SM00055 | | S | | SM00057 | | | S | 050-099 |
| 066 | 18 | | PA | | 3-9 | 33-24-12 | SM00093 | | S | | SM00073 | | | S | 150-199 |
| 066 | 18 | | PA | | 3-3 | 33-24-12 | SM00093 | | S | | SM00073 | | | S | 275-278 |
| 066 | 18 | | PA | | 2-10 | 33-24-12 | SM00093 | | S | | SM00073 | | | S | 280-299 |
| 067 | 18 | | PA | | 4-5 | 33-24-12 | SM00056 | | S | | SM00058 | | | S | 050-099 |
| 067 | 18 | | PA | | 3-9 | 33-24-12 | SM00094 | | S | | SM00074 | | | S | 150-199 |
| 067 | 18 | | PA | | 3-3 | 33-24-12 | SM00094 | | S | | SM00074 | | | S | 275-278 |
| 067 | 18 | | PA | | 2-10 | 33-24-12 | SM00094 | | S | | SM00074 | | | S | 280-299 |
| 068 | 22 | | PA | | 1-8 | 33-24-12 | SM00058 | | S | | D03374 | | 3 | | 050-099 |
| 068 | 20 | | PA | | 1-11 | 33-24-12 | SM00074 | | S | | D03232 | | 3 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 32

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | | |
| 068 | 20 | PA | | 2-9 | 33-24-12 | SM00074 | | S | | D03232 | 3 | | | 275-278 | | |
| 068 | 20 | PA | | 3-5 | 33-24-12 | SM00074 | | S | | D03232 | 3 | | | 280-299 | | |
| 069 | 22 | PA | | 1-8 | 33-24-12 | SM00057 | | S | | D03374 | 4 | | | 050-099 | | |
| 069 | 20 | PA | | 1-11 | 33-24-12 | SM00073 | | S | | D03232 | 4 | | | 150-199 | | |
| 069 | 20 | PA | | 2-9 | 33-24-12 | SM00073 | | S | | D03232 | 4 | | | 275-278 | | |
| 069 | 20 | PA | | 3-5 | 33-24-12 | SM00073 | | S | | D03232 | 4 | | | 280-299 | | |
| 070 | 20 | PA | | 1-7 | 33-24-12 | GD02170 | | A.. | E | D03374 | 5 | | | 050-099 | | |
| 070 | 20 | PA | | 1-10 | 33-24-12 | GD05654 | | A.. | E | D03232 | 5 | | | 150-199 | | |
| 070 | 20 | PA | | 2-5 | 33-24-12 | GD05008 | | A.. | E | D03232 | 5 | | | 275-278 | | |
| 070 | 20 | PA | | 2-4 | 33-24-12 | GD05008 | | A.. | E | D03232 | 5 | | | 280-299 | | |
| 071 | 22 | PA | | 3-1 | 33-24-12 | SM00057 | | | S | D03376 | 4 | | | 050-099 | | |
| 072 | 22 | PA | | 3-1 | 33-24-12 | SM00058 | | | S | D03376 | 3 | | | 050-099 | | |
| 073 | 20 | PA | | 3-2 | 33-24-12 | SM00074 | | | S | D03234 | 3 | | | 150-199 | | |
| 074 | 20 | PA | | 3-2 | 33-24-12 | SM00073 | | | S | D03234 | 4 | | | 150-199 | | |
| 075 | 20 | PA | | 3-0 | 33-24-12 | GD02170 | | A.. | E | D03376 | 5 | | | 050-099 | | |
| 075 | 20 | PA | | 4-4 | 33-24-12 | GD05654 | | A.. | E | D03234 | 5 | | | 150-199 | | |
| 076 | 18 | PA | | 6-8 | 33-24-12 | SM00073 | | | S | SM00077 | | | S | 150-199 | | |
| 076 | 18 | PA | | 18-11 | 33-24-12 | SM00073 | | | S | SM00077 | | | S | 275-278 | | |
| 076 | 18 | PA | | 18-5 | 33-24-12 | SM00073 | | | S | SM00077 | | | S | 280-299 | | |
| 077 | 18 | PA | | 6-8 | 33-24-12 | SM00074 | | | S | SM00078 | | | S | 150-199 | | |
| 077 | 18 | PA | | 18-11 | 33-24-12 | SM00074 | | | S | SM00078 | | | S | 275-278 | | |
| 077 | 18 | PA | | 18-5 | 33-24-12 | SM00074 | | | S | SM00078 | | | S | 280-299 | | |
| 078 | 20 | PA | | 2-9 | 33-24-12 | SM00078 | | | S | D03236 | 3 | | | 150-199 | | |
| 079 | 20 | PA | | 2-9 | 33-24-12 | SM00077 | | | S | D03236 | 4 | | | 150-199 | | |
| 080 | 20 | PA | | 4-8 | 33-24-12 | GD05134 | | A.. | E | D03236 | 5 | | | 150-199 | | |
| 083 | 20 | PA | | 2-3 | 33-24-12 | SM00078 | | | S | D03238 | 3 | | | 150-199 | | |
| 083 | 20 | PA | | 9-0 | 33-24-12 | SM00078 | | | S | D03238 | 3 | | | 275-299 | | |
| 084 | 20 | PA | | 2-3 | 33-24-12 | SM00077 | | | S | D03238 | 4 | | | 150-199 | | |
| 084 | 20 | PA | | 9-0 | 33-24-12 | SM00077 | | | S | D03238 | 4 | | | 275-299 | | |
| 085 | 20 | PA | | 2-3 | 33-24-12 | GD05134 | | A.. | E | D03238 | 5 | | | 150-199 | | |
| 085 | 20 | PA | | 3-11 | 33-24-12 | GD05482 | | A.. | E | D03238 | 5 | | | 275-299 | | |
| 086 | 18 | PA | | 14-11 | 33-24-12 | SM00077 | | | S | SM00081 | | | S | 150-199 | | |
| 086 | 18 | PA | | 5-3 | 33-24-12 | SM00077 | | | S | SM00081 | | | S | 275-299 | | |
| 087 | 18 | PA | | 14-11 | 33-24-12 | SM00078 | | | S | SM00082 | | | S | 150-199 | | |
| 087 | 18 | PA | | 5-3 | 33-24-12 | SM00078 | | | S | SM00082 | | | S | 275-299 | | |
| 088 | 20 | PA | | 12-2 | 33-24-12 | SM00082 | | | S | D03240 | 3 | | | 150-199 | | |
| 088 | 20 | PA | | 3-0 | 33-24-12 | SM00082 | | | S | D03240 | 3 | | | 275-299 | | |
| 089 | 20 | PA | | 12-2 | 33-24-12 | SM00081 | | | S | D03240 | 4 | | | 150-199 | | |
| 089 | 20 | PA | | 3-0 | 33-24-12 | SM00081 | | | S | D03240 | 4 | | | 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 33

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | |
| 090 | 20 | | PA | | 3-9 | 33-24-12 | GD05134 | A.. | E | | D03240 | | | | 150-199 |
| 090 | 20 | | PA | | 4-5 | 33-24-12 | GD05012 | A.. | E | | D03240 | | | | 275-299 |
| 093 | 20 | | PA | | 1-10 | 33-24-12 | SM00082 | | S | | D03242 | | | | 275-299 |
| 094 | 20 | | PA | | 1-10 | 33-24-12 | SM00081 | | S | | D03242 | | | | 275-299 |
| 095 | 20 | | PA | | 1-11 | 33-24-12 | GD05012 | A.. | E | | D03242 | | | | 275-299 |
| 096 | 18 | | PA | | 7-8 | 33-24-12 | SM00081 | | S | | SM00085 | | | S | 150-199 |
| 096 | 18 | | PA | | 4-9 | 33-24-12 | SM00081 | | S | | SM00085 | | | S | 275-278 |
| 096 | 18 | | PA | | 5-3 | 33-24-12 | SM00081 | | S | | SM00085 | | | S | 280-299 |
| 097 | 18 | | PA | | 7-8 | 33-24-12 | SM00082 | | S | | SM00086 | | | S | 150-199 |
| 097 | 18 | | PA | | 4-9 | 33-24-12 | SM00082 | | S | | SM00086 | | | S | 275-278 |
| 097 | 18 | | PA | | 5-3 | 33-24-12 | SM00082 | | S | | SM00086 | | | S | 280-299 |
| 098 | 20 | | PA | | 1-9 | 33-24-12 | SM00086 | | S | | D03244 | | | 3 | 275-299 |
| 099 | 20 | | PA | | 1-9 | 33-24-12 | SM00085 | | S | | D03244 | | | 4 | 275-299 |
| 100 | 20 | | PA | | 3-9 | 33-24-12 | GD05012 | A.. | E | | D03244 | | | 5 | 275-299 |
| 103 | 20 | | PA | | 2-9 | 33-24-12 | SM00086 | | S | | D03246 | | | 3 | 150-199 |
| 103 | 20 | | PA | | 3-3 | 33-24-12 | SM00086 | | S | | D03246 | | | 3 | 275-299 |
| 104 | 20 | | PA | | 2-9 | 33-24-12 | SM00085 | | S | | D03246 | | | 4 | 150-199 |
| 104 | 20 | | PA | | 3-3 | 33-24-12 | SM00085 | | S | | D03246 | | | 4 | 275-299 |
| 105 | 20 | | PA | | 2-1 | 33-24-12 | GD05656 | A.. | E | | D03246 | | | 5 | 150-199 |
| 105 | 20 | | PA | | 4-3 | 33-24-12 | GD05016 | A.. | E | | D03246 | | | 5 | 275-299 |
| 106 | 18 | | PA | | 2-3 | 33-24-12 | SM00085 | | S | | SM00095 | | | S | 150-199 |
| 106 | 18 | | PA | | 7-1 | 33-24-12 | SM00085 | | S | | SM00095 | | | S | 275-299 |
| 107 | 18 | | PA | | 2-3 | 33-24-12 | SM00086 | | S | | SM00096 | | | S | 150-199 |
| 107 | 18 | | PA | | 7-1 | 33-24-12 | SM00086 | | S | | SM00096 | | | S | 275-299 |
| 108 | 20 | | PA | | 2-2 | 33-24-12 | SM00096 | | S | | D03248 | | | 3 | 150-199 |
| 108 | 20 | | PA | | 2-10 | 33-24-12 | SM00096 | | S | | D03248 | | | 3 | 275-299 |
| 109 | 20 | | PA | | 2-2 | 33-24-12 | SM00095 | | S | | D03248 | | | 4 | 150-199 |
| 109 | 20 | | PA | | 2-10 | 33-24-12 | SM00095 | | S | | D03248 | | | 4 | 275-299 |
| 110 | 20 | | PA | | 3-3 | 33-24-12 | GD05658 | A.. | E | | D03248 | | | 5 | 150-199 |
| 110 | 20 | | PA | | 1-10 | 33-24-12 | GD05016 | A.. | E | | D03248 | | | 5 | 275-299 |
| 121 | 20 | | PA | | 1-10 | 33-24-12 | SM00094 | | S | | D08146 | | | 3 | 150-199 |
| 121 | 20 | | PA | | 2-11 | 33-24-12 | SM00094 | | S | | D08146 | | | 3 | 275-278 |
| 121 | 20 | | PA | | 2-9 | 33-24-12 | SM00094 | | S | | D08146 | | | 3 | 280-299 |
| 122 | 20 | | PA | | 1-10 | 33-24-12 | SM00093 | | S | | D08146 | | | 4 | 150-199 |
| 122 | 20 | | PA | | 2-11 | 33-24-12 | SM00093 | | S | | D08146 | | | 4 | 275-278 |
| 122 | 20 | | PA | | 2-9 | 33-24-12 | SM00093 | | S | | D08146 | | | 4 | 280-299 |
| 123 | 20 | | PA | | 4-6 | 33-24-12 | GD05654 | A.. | E | | D08146 | | | 5 | 150-199 |
| 123 | 20 | | PA | | 3-1 | 33-24-12 | GD05008 | A.. | E | | D08146 | | | 5 | 275-278 |
| 123 | 20 | | PA | | 3-3 | 33-24-12 | GD05008 | A.. | E | | D08146 | | | 5 | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 34

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | |
| 125 | 18 | | PA | 5-4 | 33-24-12 | SM00095 | | | S | | SM00099 | | | S | 150-199 |
| 125 | 18 | | PA | 5-11 | 33-24-12 | SM00095 | | | S | | SM00099 | | | S | 275-278 |
| 125 | 18 | | PA | 6-5 | 33-24-12 | SM00095 | | | S | | SM00099 | | | S | 280-299 |
| 126 | 18 | | PA | 5-4 | 33-24-12 | SM00096 | | | S | | SM00100 | | | S | 150-199 |
| 126 | 18 | | PA | 5-11 | 33-24-12 | SM00096 | | | S | | SM00100 | | | S | 275-278 |
| 126 | 18 | | PA | 6-5 | 33-24-12 | SM00096 | | | S | | SM00100 | | | S | 280-299 |
| 129 | 18 | | PA | 6-1 | 33-24-12 | SM00099 | | | S | | SM00103 | | | S | 150-199 |
| 129 | 18 | | PA | 5-0 | 33-24-12 | SM00099 | | | S | | SM00103 | | | S | 275-278 |
| 129 | 18 | | PA | 5-6 | 33-24-12 | SM00099 | | | S | | SM00103 | | | S | 280-299 |
| 130 | 18 | | PA | 6-1 | 33-24-12 | SM00100 | | | S | | SM00104 | | | S | 150-199 |
| 130 | 18 | | PA | 5-0 | 33-24-12 | SM00100 | | | S | | SM00104 | | | S | 275-278 |
| 130 | 18 | | PA | 5-6 | 33-24-12 | SM00100 | | | S | | SM00104 | | | S | 280-299 |
| 133 | 18 | | PA | 5-9 | 33-24-12 | SM00103 | | | S | | SM00107 | | | S | 150-199 |
| 133 | 18 | | PA | 7-1 | 33-24-12 | SM00103 | | | S | | SM00107 | | | S | 275-299 |
| 134 | 18 | | PA | 5-9 | 33-24-12 | SM00104 | | | S | | SM00108 | | | S | 150-199 |
| 134 | 18 | | PA | 7-1 | 33-24-12 | SM00104 | | | S | | SM00108 | | | S | 275-299 |
| 137 | 18 | | PA | 5-10 | 33-24-12 | SM00107 | | | S | | SM00111 | | | S | 150-199, 275-278 |
| 137 | 18 | | PA | 6-4 | 33-24-12 | SM00107 | | | S | | SM00111 | | | S | 280-299 |
| 138 | 18 | | PA | 5-10 | 33-24-12 | SM00108 | | | S | | SM00112 | | | S | 150-199, 275-278 |
| 138 | 18 | | PA | 6-4 | 33-24-12 | SM00108 | | | S | | SM00112 | | | S | 280-299 |
| 141 | 18 | | PA | 4-7 | 33-24-12 | SM00111 | | | S | | SM00115 | | | S | 150-199 |
| 141 | 18 | | PA | 5-2 | 33-24-12 | SM00111 | | | S | | SM00115 | | | S | 275-278 |
| 141 | 18 | | PA | 5-8 | 33-24-12 | SM00111 | | | S | | SM00115 | | | S | 280-299 |
| 142 | 18 | | PA | 4-7 | 33-24-12 | SM00112 | | | S | | SM00116 | | | S | 150-199 |
| 142 | 18 | | PA | 5-2 | 33-24-12 | SM00112 | | | S | | SM00116 | | | S | 275-278 |
| 142 | 18 | | PA | 5-8 | 33-24-12 | SM00112 | | | S | | SM00116 | | | S | 280-299 |
| 145 | 18 | | PA | 7-3 | 33-24-12 | SM00115 | | | S | | SM00119 | | | S | 150-199 |
| 145 | 18 | | PA | 6-10 | 33-24-12 | SM00115 | | | S | | SM00119 | | | S | 275-299 |
| 146 | 18 | | PA | 7-3 | 33-24-12 | SM00116 | | | S | | SM00120 | | | S | 150-199 |
| 146 | 18 | | PA | 6-10 | 33-24-12 | SM00116 | | | S | | SM00120 | | | S | 275-299 |
| 149 | 18 | | PA | 5-1 | 33-24-12 | SM00119 | | | S | | SM00123 | | | S | 150-199 |
| 149 | 18 | | PA | 4-6 | 33-24-12 | SM00119 | | | S | | SM00123 | | | S | 275-278 |
| 149 | 18 | | PA | 5-0 | 33-24-12 | SM00119 | | | S | | SM00123 | | | S | 280-299 |
| 150 | 18 | | PA | 5-1 | 33-24-12 | SM00120 | | | S | | SM00124 | | | S | 150-199 |
| 150 | 18 | | PA | 4-6 | 33-24-12 | SM00120 | | | S | | SM00124 | | | S | 275-278 |
| 150 | 18 | | PA | 5-0 | 33-24-12 | SM00120 | | | S | | SM00124 | | | S | 280-299 |
| 153 | 18 | | PA | 6-2 | 33-24-12 | SM00123 | | | S | | SM00127 | | | S | 150-199 |
| 153 | 18 | | PA | 3-5 | 33-24-12 | SM00123 | | | S | | SM00127 | | | S | 275-278 |
| 153 | 18 | | PA | 6-3 | 33-24-12 | SM00123 | | | S | | SM00127 | | | S | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 35

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | |
| 154 | 18 | | PA | | 6-2 | 33-24-12 | SM00124 | | S | | SM00128 | | S | | 150-199 |
| 154 | 18 | | PA | | 3-5 | 33-24-12 | SM00124 | | S | | SM00128 | | S | | 275-278 |
| 154 | 18 | | PA | | 6-3 | 33-24-12 | SM00124 | | S | | SM00128 | | S | | 280-299 |
| 157 | 18 | | PA | | 3-11 | 33-24-12 | SM00127 | | S | | SM00129 | | S | | 150-199 |
| 157 | 18 | | PA | | 7-1 | 33-24-12 | SM00127 | | S | | SM00129 | | S | | 275-278 |
| 157 | 18 | | PA | | 4-8 | 33-24-12 | SM00127 | | S | | SM00129 | | S | | 280-299 |
| 158 | 18 | | PA | | 3-11 | 33-24-12 | SM00128 | | S | | SM00130 | | S | | 150-199 |
| 158 | 18 | | PA | | 7-1 | 33-24-12 | SM00128 | | S | | SM00130 | | S | | 275-278 |
| 158 | 18 | | PA | | 4-8 | 33-24-12 | SM00128 | | S | | SM00130 | | S | | 280-299 |
| 161 | 20 | | PA | | 2-6 | 33-24-12 | SM00096 | | S | | D03348 | 3 | | | 150-199 |
| 161 | 20 | | PA | | 1-8 | 33-24-12 | SM00096 | | S | | D03348 | 3 | | | 275-299 |
| 162 | 20 | | PA | | 2-6 | 33-24-12 | SM00095 | | S | | D03348 | 4 | | | 150-199 |
| 162 | 20 | | PA | | 1-8 | 33-24-12 | SM00095 | | S | | D03348 | 4 | | | 275-299 |
| 163 | 20 | | PA | | 2-6 | 33-24-12 | GD05658 | A.. | E | | D03348 | 5 | | | 150-199 |
| 163 | 20 | | PA | | 3-11 | 33-24-12 | GD05016 | A.. | E | | D03348 | 5 | | | 275-299 |
| 164 | 20 | | PA | | 2-10 | 33-24-12 | SM00100 | | S | | D03350 | 3 | | | 150-199, 275-299 |
| 165 | 20 | | PA | | 2-10 | 33-24-12 | SM00099 | | S | | D03350 | 4 | | | 150-199, 275-299 |
| 166 | 20 | | PA | | 4-4 | 33-24-12 | GD05020 | A.. | E | | D03350 | 5 | | | 150-199, 275-299 |
| 167 | 20 | | PA | | 2-0 | 33-24-12 | SM00100 | | S | | D03352 | 3 | | | 150-199, 275-299 |
| 168 | 20 | | PA | | 2-0 | 33-24-12 | SM00099 | | S | | D03352 | 4 | | | 150-199, 275-299 |
| 169 | 20 | | PA | | 1-11 | 33-24-12 | GD05020 | A.. | E | | D03352 | 5 | | | 150-199, 275-299 |
| 170 | 20 | | PA | | 3-5 | 33-24-12 | SM00104 | | S | | D03354 | 3 | | | 150-199 |
| 170 | 20 | | PA | | 2-0 | 33-24-12 | SM00104 | | S | | D03354 | 3 | | | 275-299 |
| 171 | 20 | | PA | | 3-5 | 33-24-12 | SM00103 | | S | | D03354 | 4 | | | 150-199 |
| 171 | 20 | | PA | | 2-0 | 33-24-12 | SM00103 | | S | | D03354 | 4 | | | 275-299 |
| 172 | 20 | | PA | | 3-9 | 33-24-12 | GD05020 | A.. | E | | D03354 | 5 | | | 150-199 |
| 172 | 20 | | PA | | 4-0 | 33-24-12 | GD05020 | A.. | E | | D03354 | 5 | | | 275-299 |
| 173 | 20 | | PA | | 1-10 | 33-24-12 | SM00104 | | S | | D03356 | 3 | | | 150-199 |
| 173 | 20 | | PA | | 2-11 | 33-24-12 | SM00104 | | S | | D03356 | 3 | | | 275-299 |
| 174 | 20 | | PA | | 1-10 | 33-24-12 | SM00103 | | S | | D03356 | 4 | | | 150-199 |
| 174 | 20 | | PA | | 2-11 | 33-24-12 | SM00103 | | S | | D03356 | 4 | | | 275-299 |
| 175 | 20 | | PA | | 4-4 | 33-24-12 | GD05024 | A.. | E | | D03356 | 5 | | | 150-199 |
| 175 | 20 | | PA | | 4-8 | 33-24-12 | GD05024 | A.. | E | | D03356 | 5 | | | 275-299 |
| 176 | 20 | | PA | | 2-9 | 33-24-12 | SM00108 | | S | | D03358 | 3 | | | 150-199 |
| 176 | 20 | | PA | | 3-1 | 33-24-12 | SM00108 | | S | | D03358 | 3 | | | 275-299 |
| 177 | 20 | | PA | | 2-9 | 33-24-12 | SM00107 | | S | | D03358 | 4 | | | 150-199 |
| 177 | 20 | | PA | | 3-1 | 33-24-12 | SM00107 | | S | | D03358 | 4 | | | 275-299 |
| 178 | 20 | | PA | | 1-10 | 33-24-12 | GD05024 | A.. | E | | D03358 | 5 | | | 150-199 |
| 178 | 20 | | PA | | 2-2 | 33-24-12 | GD05024 | A.. | E | | D03358 | 5 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 36

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | |
| 179 | 20 | | PA | | 1-9 | 33-24-12 | SM00108 | | | S | | D08148 | 3 | | 150-199, 275-299 |
| 180 | 20 | | PA | | 1-9 | 33-24-12 | SM00107 | | | S | | D08148 | 4 | | 150-199, 275-299 |
| 181 | 20 | | PA | | 3-9 | 33-24-12 | GD05024 | | A.. | E | | D08148 | 5 | | 150-199, 275-299 |
| 182 | 20 | | PA | | 2-9 | 33-24-12 | SM00112 | | | S | | D08150 | 3 | | 150-199 |
| 182 | 20 | | PA | | 3-1 | 33-24-12 | SM00112 | | | S | | D08150 | 3 | | 275-299 |
| 183 | 20 | | PA | | 2-9 | 33-24-12 | SM00111 | | | S | | D08150 | 4 | | 150-199 |
| 183 | 20 | | PA | | 3-1 | 33-24-12 | SM00111 | | | S | | D08150 | 4 | | 275-299 |
| 184 | 20 | | PA | | 4-6 | 33-24-12 | GD05028 | | A.. | E | | D08150 | 5 | | 150-199 |
| 184 | 20 | | PA | | 4-10 | 33-24-12 | GD05028 | | A.. | E | | D08150 | 5 | | 275-299 |
| 185 | 20 | | PA | | 2-2 | 33-24-12 | SM00112 | | | S | | D08152 | 3 | | 150-199, 275-299 |
| 186 | 20 | | PA | | 2-2 | 33-24-12 | SM00111 | | | S | | D08152 | 4 | | 150-199, 275-299 |
| 187 | 20 | | PA | | 2-0 | 33-24-12 | GD05028 | | A.. | E | | D08152 | 5 | | 150-199, 275-299 |
| 188 | 20 | | PA | | 1-10 | 33-24-12 | SM00116 | | | S | | D08154 | 3 | | 150-199 |
| 188 | 20 | | PA | | 2-5 | 33-24-12 | SM00116 | | | S | | D08154 | 3 | | 275-299 |
| 189 | 20 | | PA | | 1-10 | 33-24-12 | SM00115 | | | S | | D08154 | 4 | | 150-199 |
| 189 | 20 | | PA | | 2-5 | 33-24-12 | SM00115 | | | S | | D08154 | 4 | | 275-299 |
| 190 | 20 | | PA | | 3-7 | 33-24-12 | GD05028 | | A.. | E | | D08154 | 5 | | 150-199, 275-299 |
| 191 | 20 | | PA | | 3-4 | 33-24-12 | SM00116 | | | S | | D03360 | 3 | | 150-199 |
| 191 | 20 | | PA | | 2-9 | 33-24-12 | SM00116 | | | S | | D03360 | 3 | | 275-299 |
| 192 | 20 | | PA | | 3-4 | 33-24-12 | SM00115 | | | S | | D03360 | 4 | | 150-199 |
| 192 | 20 | | PA | | 2-9 | 33-24-12 | SM00115 | | | S | | D03360 | 4 | | 275-299 |
| 193 | 20 | | PA | | 4-5 | 33-24-12 | GD05032 | | A.. | E | | D03360 | 5 | | 150-199, 275-299 |
| 194 | 20 | | PA | | 2-10 | 33-24-12 | SM00120 | | | S | | D03362 | 3 | | 150-199 |
| 194 | 20 | | PA | | 3-0 | 33-24-12 | SM00120 | | | S | | D03362 | 3 | | 275-299 |
| 195 | 20 | | PA | | 2-10 | 33-24-12 | SM00119 | | | S | | D03362 | 4 | | 150-199 |
| 195 | 20 | | PA | | 3-0 | 33-24-12 | SM00119 | | | S | | D03362 | 4 | | 275-299 |
| 196 | 20 | | PA | | 2-0 | 33-24-12 | GD05032 | | A.. | E | | D03362 | 5 | | 150-199, 275-299 |
| 197 | 20 | | PA | | 1-9 | 33-24-12 | SM00120 | | | S | | D03364 | 3 | | 150-199 |
| 197 | 20 | | PA | | 1-6 | 33-24-12 | SM00120 | | | S | | D03364 | 3 | | 275-299 |
| 198 | 20 | | PA | | 1-9 | 33-24-12 | SM00119 | | | S | | D03364 | 4 | | 150-199 |
| 198 | 20 | | PA | | 1-6 | 33-24-12 | SM00119 | | | S | | D03364 | 4 | | 275-299 |
| 199 | 20 | | PA | | 3-9 | 33-24-12 | GD05032 | | A.. | E | | D03364 | 5 | | 150-199, 275-299 |
| 201B | 22 | | PB | A | 15-9 | 23-31-15 | D05104P | | | 2 | | SM00008 | | S | 050-099 |
| 201B | 22 | | PB | IA | 3-10 | 23-31-15 | D06514P | | | 2 | | SM00002 | | S | 280-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-15 | D05104P | | | 1 | | SM00007 | | S | 050-099 |
| 201R | 22 | | PB | IA | 0-0 | 23-31-15 | D06514P | | | 1 | | SM00001 | | S | 280-299 |
| 202B | 22 | | PB | IB | 3-9 | 23-31-15 | D03226 | | | 2 | | SM00002 | | S | 280-299 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-15 | D03226 | | | 1 | | SM00001 | | S | 280-299 |
| 203B | 22 | | PB | IC | 5-1 | 23-31-15 | SM00002 | | | S | | SM00004 | | S | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 37

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | |
| 203R | 22 | PB | IC | | 0-0 | 23-31-15 | SM00001 | | S | | SM00003 | | S | | 280-299 |
| 204B | 22 | PB | ID | | 1-5 | 23-31-15 | D03228 | 2 | | | SM00002 | | S | | 280-299 |
| 204R | 22 | PB | ID | | 0-0 | 23-31-15 | D03228 | 1 | | | SM00001 | | S | | 280-299 |
| 205B | 22 | PB | IE | | 2-10 | 23-31-15 | SM00004 | | S | | SM00008 | | S | | 280-299 |
| 205R | 22 | PB | IE | | 0-0 | 23-31-15 | SM00003 | | S | | SM00007 | | S | | 280-299 |
| 206B | 22 | PB | F | | 3-7 | 23-31-15 | SM00008 | | S | | D03352 | 2 | | | 050-099 |
| 206B | 22 | PB | IF | | 2-3 | 23-31-15 | SM00004 | | S | | D03230 | 2 | | | 280-299 |
| 206R | 22 | PB | F | | 0-0 | 23-31-15 | SM00007 | | S | | D03352 | 1 | | | 050-099 |
| 206R | 22 | PB | IF | | 0-0 | 23-31-15 | SM00003 | | S | | D03230 | 1 | | | 280-299 |
| 208B | 22 | PB | H | | 2-0 | 23-31-15 | SM00008 | | S | | D03354 | 2 | | | 050-099 |
| 208B | 22 | PB | IH | | 2-9 | 23-31-15 | SM00004 | | S | | D08146 | 2 | | | 280-299 |
| 208R | 22 | PB | H | | 0-0 | 23-31-15 | SM00007 | | S | | D03354 | 1 | | | 050-099 |
| 208R | 22 | PB | IH | | 0-0 | 23-31-15 | SM00003 | | S | | D08146 | 1 | | | 280-299 |
| 209B | 22 | PB | J | | 3-7 | 23-31-15 | SM00008 | | S | | SM00012 | | S | | 050-099 |
| 209B | 22 | PB | II | | 18-5 | 23-31-15 | SM00008 | | S | | SM00012 | | S | | 280-299 |
| 209R | 22 | PB | J | | 0-0 | 23-31-15 | SM00007 | | S | | SM00011 | | S | | 050-099 |
| 209R | 22 | PB | II | | 0-0 | 23-31-15 | SM00007 | | S | | SM00011 | | S | | 280-299 |
| 210B | 22 | PB | K | | 1-11 | 23-31-15 | SM00012 | | S | | D03356 | 2 | | | 050-099 |
| 210B | 22 | PB | IJ | | 3-5 | 23-31-15 | SM00008 | | S | | D03232 | 2 | | | 280-299 |
| 210R | 22 | PB | K | | 0-0 | 23-31-15 | SM00011 | | S | | D03356 | 1 | | | 050-099 |
| 210R | 22 | PB | IJ | | 0-0 | 23-31-15 | SM00007 | | S | | D03232 | 1 | | | 280-299 |
| 212B | 22 | PB | M | | 2-10 | 23-31-15 | SM00012 | | S | | D03358 | 2 | | | 050-099 |
| 212R | 22 | PB | M | | 0-0 | 23-31-15 | SM00011 | | S | | D03358 | 1 | | | 050-099 |
| 213B | 22 | PB | N | | 5-11 | 23-31-15 | SM00012 | | S | | SM00016 | | S | | 050-099 |
| 213B | 22 | PB | IM | | 5-3 | 23-31-15 | SM00012 | | S | | SM00016 | | S | | 280-299 |
| 213R | 22 | PB | N | | 0-0 | 23-31-15 | SM00011 | | S | | SM00015 | | S | | 050-099 |
| 213R | 22 | PB | IM | | 0-0 | 23-31-15 | SM00011 | | S | | SM00015 | | S | | 280-299 |
| 214B | 22 | PB | P | | 2-2 | 23-31-15 | SM00016 | | S | | D03360 | 2 | | | 050-099 |
| 214R | 22 | PB | P | | 0-0 | 23-31-15 | SM00015 | | S | | D03360 | 1 | | | 050-099 |
| 216B | 22 | PB | S | | 2-11 | 23-31-15 | SM00016 | | S | | D03362 | 2 | | | 050-099 |
| 216B | 22 | PB | IP | | 9-0 | 23-31-15 | SM00012 | | S | | D03238 | 2 | | | 280-299 |
| 216R | 22 | PB | S | | 0-0 | 23-31-15 | SM00015 | | S | | D03362 | 1 | | | 050-099 |
| 216R | 22 | PB | IP | | 0-0 | 23-31-15 | SM00011 | | S | | D03238 | 1 | | | 280-299 |
| 217B | 22 | PB | T | | 6-2 | 23-31-15 | SM00016 | | S | | SM00020 | | S | | 050-099 |
| 217B | 22 | PB | IQ | | 5-3 | 23-31-15 | SM00016 | | S | | SM00020 | | S | | 280-299 |
| 217R | 22 | PB | T | | 0-0 | 23-31-15 | SM00015 | | S | | SM00019 | | S | | 050-099 |
| 217R | 22 | PB | IQ | | 0-0 | 23-31-15 | SM00015 | | S | | SM00019 | | S | | 280-299 |
| 218B | 22 | PB | U | | 2-1 | 23-31-15 | SM00020 | | S | | D03364 | 2 | | | 050-099 |
| 218B | 22 | PB | IR | | 3-0 | 23-31-15 | SM00016 | | S | | D03240 | 2 | | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 38

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | | | |
| 218R | 22 | PB | U | 0-0 | 23-31-15 | SM00019 | | | | | | | D03364 | 1 | | | 050-099 |
| 218R | 22 | PB | IR | 0-0 | 23-31-15 | SM00015 | | | | | | | D03240 | 1 | | | 280-299 |
| 220B | 22 | PB | W | 2-6 | 23-31-15 | SM00020 | | | | | | | D03366 | 2 | | | 050-099 |
| 220B | 22 | PB | IT | 1-10 | 23-31-15 | SM00016 | | | | | | | D03242 | 2 | | | 280-299 |
| 220R | 22 | PB | W | 0-0 | 23-31-15 | SM00019 | | | | | | | D03366 | 1 | | | 050-099 |
| 220R | 22 | PB | IT | 0-0 | 23-31-15 | SM00015 | | | | | | | D03242 | 1 | | | 280-299 |
| 221B | 22 | PB | X | 5-8 | 23-31-15 | SM00020 | | | | | | | SM00024 | | S | | 050-099 |
| 221B | 22 | PB | Y | 2-2 | 23-31-15 | D06514P | | 2 | | | | | SM00171 | | S | | 150-199 |
| 221B | 22 | PB | Y | 3-0 | 23-31-15 | D06514P | | 2 | | | | | SM00023 | | S | | 275-278 |
| 221B | 22 | PB | Y | 7-1 | 23-31-15 | SM00020 | | | | | | | SM00024 | | S | | 280-299 |
| 221R | 22 | PB | X | 0-0 | 23-31-15 | SM00019 | | | | | | | SM00023 | | S | | 050-099 |
| 221R | 22 | PB | Y | 0-0 | 23-31-15 | D06514P | | 1 | | | | | SM00170 | | S | | 150-199 |
| 221R | 22 | PB | Y | 0-0 | 23-31-15 | D06514P | | 1 | | | | | SM00024 | | S | | 275-278 |
| 221R | 22 | PB | Y | 0-0 | 23-31-15 | SM00019 | | | | | | | SM00023 | | S | | 280-299 |
| 222B | 22 | PB | Y | 2-1 | 23-31-15 | SM00024 | | | | | | | D03368 | 2 | | | 050-099 |
| 222B | 22 | PB | AA | 2-5 | 23-31-15 | SM00023 | | | | | | | D03226 | 2 | | | 275-278 |
| 222B | 22 | PB | AA | 1-9 | 23-31-15 | SM00020 | | | | | | | D03244 | 2 | | | 280-299 |
| 222R | 22 | PB | Y | 0-0 | 23-31-15 | SM00023 | | | | | | | D03368 | 1 | | | 050-099 |
| 222R | 22 | PB | AA | 0-0 | 23-31-15 | SM00024 | | | | | | | D03226 | 1 | | | 275-278 |
| 222R | 22 | PB | AA | 0-0 | 23-31-15 | SM00019 | | | | | | | D03244 | 1 | | | 280-299 |
| 224B | 22 | PB | AB | 2-8 | 23-31-15 | SM00024 | | | | | | | D03370 | 2 | | | 050-099 |
| 224B | 22 | PB | AC | 2-6 | 23-31-15 | SM00023 | | | | | | | D03228 | 2 | | | 275-278 |
| 224B | 22 | PB | AC | 3-3 | 23-31-15 | SM00020 | | | | | | | D03246 | 2 | | | 280-299 |
| 224R | 22 | PB | AB | 0-0 | 23-31-15 | SM00023 | | | | | | | D03370 | 1 | | | 050-099 |
| 224R | 22 | PB | AC | 0-0 | 23-31-15 | SM00024 | | | | | | | D03228 | 1 | | | 275-278 |
| 224R | 22 | PB | AC | 0-0 | 23-31-15 | SM00019 | | | | | | | D03246 | 1 | | | 280-299 |
| 225B | 22 | PB | AC | 5-9 | 23-31-15 | SM00024 | | | | | | | SM00028 | | S | | 050-099 |
| 225B | 22 | PB | AD | 5-5 | 23-31-15 | SM00023 | | | | | | | SM00171 | | S | | 275-278 |
| 225B | 22 | PB | AD | 6-5 | 23-31-15 | SM00024 | | | | | | | SM00028 | | S | | 280-299 |
| 225R | 22 | PB | AC | 0-0 | 23-31-15 | SM00023 | | | | | | | SM00027 | | S | | 050-099 |
| 225R | 22 | PB | AD | 0-0 | 23-31-15 | SM00024 | | | | | | | SM00170 | | S | | 275-278 |
| 225R | 22 | PB | AD | 0-0 | 23-31-15 | SM00023 | | | | | | | SM00027 | | S | | 280-299 |
| 226B | 22 | PB | AD | 1-10 | 23-31-15 | SM00028 | | | | | | | D03372 | 2 | | | 050-099 |
| 226B | 22 | PB | AE | 2-1 | 23-31-15 | SM00171 | | | | | | | D03230 | 2 | | | 275-278 |
| 226B | 22 | PB | AE | 2-10 | 23-31-15 | SM00024 | | | | | | | D03248 | 2 | | | 280-299 |
| 226R | 22 | PB | AD | 0-0 | 23-31-15 | SM00027 | | | | | | | D03372 | 1 | | | 050-099 |
| 226R | 22 | PB | AE | 0-0 | 23-31-15 | SM00170 | | | | | | | D03230 | 1 | | | 275-278 |
| 226R | 22 | PB | AE | 0-0 | 23-31-15 | SM00023 | | | | | | | D03248 | 1 | | | 280-299 |
| 228B | 22 | PB | AF | 3-1 | 23-31-15 | SM00028 | | | | | | | D03374 | 2 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 39

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | |
| 228B | 22 | PB | AG | 1-11 | 23-31-15 | SM00030 | | S | | D03232 | 2 | | | 150-199 | |
| 228B | 22 | PB | AG | 2-9 | 23-31-15 | SM00030 | | S | | D03232 | 2 | | | 275-278 | |
| 228B | 22 | PB | AG | 1-8 | 23-31-15 | SM00024 | | S | | D03348 | 2 | | | 280-299 | |
| 228R | 22 | PB | AF | 0-0 | 23-31-15 | SM00027 | | S | | D03374 | 1 | | | 050-099 | |
| 228R | 22 | PB | AG | 0-0 | 23-31-15 | SM00029 | | S | | D03232 | 1 | | | 150-199, 275-278 | |
| 228R | 22 | PB | AG | 0-0 | 23-31-15 | SM00023 | | S | | D03348 | 1 | | | 280-299 | |
| 229B | 22 | PB | JD | 4-8 | 23-31-15 | SM00028 | | S | | SM00032 | | S | | 050-099 | |
| 229B | 22 | PB | JD | 5-6 | 23-31-15 | SM00028 | | S | | SM00032 | | S | | 280-299 | |
| 229R | 22 | PB | JD | 0-0 | 23-31-15 | SM00027 | | S | | SM00031 | | S | | 050-099, 280-299 | |
| 230B | 22 | PB | AH | 1-5 | 23-31-15 | SM00032 | | S | | D03376 | 2 | | | 050-099 | |
| 230B | 22 | PB | AJ | 3-2 | 23-31-15 | SM00030 | | S | | D03234 | 2 | | | 150-199 | |
| 230B | 22 | PB | AJ | 2-10 | 23-31-15 | SM00028 | | S | | D03350 | 2 | | | 280-299 | |
| 230R | 22 | PB | AH | 0-0 | 23-31-15 | SM00031 | | S | | D03376 | 1 | | | 050-099 | |
| 230R | 22 | PB | AJ | 0-0 | 23-31-15 | SM00029 | | S | | D03234 | 1 | | | 150-199 | |
| 230R | 22 | PB | AJ | 0-0 | 23-31-15 | SM00027 | | S | | D03350 | 1 | | | 280-299 | |
| 231B | 22 | PB | AK | 6-8 | 23-31-15 | SM00030 | | S | | SM00034 | | S | | 150-199 | |
| 231B | 22 | PB | AK | 18-11 | 23-31-15 | SM00030 | | S | | SM00034 | | S | | 275-278 | |
| 231R | 22 | PB | AK | 0-0 | 23-31-15 | SM00029 | | S | | SM00033 | | S | | 150-199, 275-278 | |
| 232B | 22 | PB | JG | 2-8 | 23-31-15 | SM00032 | | S | | D12020 | 2 | | | 050-099 | |
| 232B | 22 | PB | AL | 2-9 | 23-31-15 | SM00034 | | S | | D03236 | 2 | | | 150-199 | |
| 232B | 22 | PB | AL | 2-0 | 23-31-15 | SM00028 | | S | | D03352 | 2 | | | 280-299 | |
| 232R | 22 | PB | JG | 0-0 | 23-31-15 | SM00031 | | S | | D12020 | 1 | | | 050-099 | |
| 232R | 22 | PB | AL | 0-0 | 23-31-15 | SM00033 | | S | | D03236 | 1 | | | 150-199 | |
| 232R | 22 | PB | AL | 0-0 | 23-31-15 | SM00027 | | S | | D03352 | 1 | | | 280-299 | |
| 233B | 22 | PB | JH | 7-1 | 23-31-15 | SM00032 | | S | | SM00036 | | S | | 280-299 | |
| 233R | 22 | PB | JH | 0-0 | 23-31-15 | SM00031 | | S | | SM00035 | | S | | 280-299 | |
| 234B | 22 | PB | AN | 2-3 | 23-31-15 | SM00034 | | S | | D03238 | 2 | | | 150-199 | |
| 234B | 22 | PB | AN | 9-0 | 23-31-15 | SM00034 | | S | | D03238 | 2 | | | 275-278 | |
| 234B | 22 | PB | AN | 2-0 | 23-31-15 | SM00032 | | S | | D03354 | 2 | | | 280-299 | |
| 234R | 22 | PB | AN | 0-0 | 23-31-15 | SM00033 | | S | | D03238 | 1 | | | 150-199, 275-278 | |
| 234R | 22 | PB | AN | 0-0 | 23-31-15 | SM00031 | | S | | D03354 | 1 | | | 280-299 | |
| 235B | 22 | PB | AP | 5-3 | 23-31-15 | SM00034 | | S | | SM00038 | | S | | 275-278 | |
| 235R | 22 | PB | AP | 0-0 | 23-31-15 | SM00033 | | S | | SM00037 | | S | | 275-278 | |
| 236B | 22 | PB | AR | 4-8 | 23-31-15 | SM00034 | | S | | D03240 | 2 | | | 150-199 | |
| 236B | 22 | PB | AR | 3-0 | 23-31-15 | SM00038 | | S | | D03240 | 2 | | | 275-278 | |
| 236B | 22 | PB | AR | 2-11 | 23-31-15 | SM00032 | | S | | D03356 | 2 | | | 280-299 | |
| 236R | 22 | PB | AR | 0-0 | 23-31-15 | SM00033 | | S | | D03240 | 1 | | | 150-199 | |
| 236R | 22 | PB | AR | 0-0 | 23-31-15 | SM00037 | | S | | D03240 | 1 | | | 275-278 | |
| 236R | 22 | PB | AR | 0-0 | 23-31-15 | SM00031 | | S | | D03356 | 1 | | | 280-299 | |

WIRE LIST

D280T132

91-21-11
Section W0800
Page 40
Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|-------|------|------|--------|-------------|---|---|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | | | | | | |
| 237B | 22 | PB | JL | | 6-4 | 23-31-15 | SM00036 | | | | | | | | | SM00040 | | S | | 280-299 |
| 237R | 22 | PB | JL | | 0-0 | 23-31-15 | SM00035 | | | | | | | | | SM00039 | | S | | 280-299 |
| 238B | 22 | PB | AU | | 1-10 | 23-31-15 | SM00038 | | | | | | | | | D03242 | 2 | | | 275-278 |
| 238B | 22 | PB | AU | | 3-1 | 23-31-15 | SM00036 | | | | | | | | | D03358 | 2 | | | 280-299 |
| 238R | 22 | PB | AU | | 0-0 | 23-31-15 | SM00037 | | | | | | | | | D03242 | 1 | | | 275-278 |
| 238R | 22 | PB | AU | | 0-0 | 23-31-15 | SM00035 | | | | | | | | | D03358 | 1 | | | 280-299 |
| 239B | 22 | PB | AV | | 4-9 | 23-31-15 | SM00038 | | | | | | | | | SM00041 | | S | | 275-278 |
| 239R | 22 | PB | AV | | 0-0 | 23-31-15 | SM00037 | | | | | | | | | SM00042 | | S | | 275-278 |
| 240B | 22 | PB | AW | | 1-9 | 23-31-15 | SM00041 | | | | | | | | | D03244 | 2 | | | 275-278 |
| 240B | 22 | PB | AW | | 1-9 | 23-31-15 | SM00036 | | | | | | | | | D08148 | 2 | | | 280-299 |
| 240R | 22 | PB | AW | | 0-0 | 23-31-15 | SM00042 | | | | | | | | | D03244 | 1 | | | 275-278 |
| 240R | 22 | PB | AW | | 0-0 | 23-31-15 | SM00035 | | | | | | | | | D08148 | 1 | | | 280-299 |
| 241B | 22 | PB | BO | | 13-10 | 23-31-15 | D05104P | | 5 | | | | | | | SM00108 | | S | | 050-099 |
| 241B | 22 | PB | JP | | 5-8 | 23-31-15 | SM00040 | | | | | | | | | SM00044 | | S | | 280-299 |
| 241R | 22 | PB | BO | | 0-0 | 23-31-15 | D05104P | | 6 | | | | | | | SM00107 | | S | | 050-099 |
| 241R | 22 | PB | JP | | 0-0 | 23-31-15 | SM00039 | | | | | | | | | SM00043 | | S | | 280-299 |
| 242B | 22 | PB | AY | | 3-11 | 23-31-15 | SM00172 | | | | | | | | | D03246 | 2 | | | 150-199 |
| 242B | 22 | PB | AY | | 3-3 | 23-31-15 | SM00041 | | | | | | | | | D03246 | 2 | | | 275-278 |
| 242B | 22 | PB | AY | | 3-1 | 23-31-15 | SM00040 | | | | | | | | | D08150 | 2 | | | 280-299 |
| 242R | 22 | PB | AY | | 0-0 | 23-31-15 | SM00173 | | | | | | | | | D03246 | 1 | | | 150-199 |
| 242R | 22 | PB | AY | | 0-0 | 23-31-15 | SM00042 | | | | | | | | | D03246 | 1 | | | 275-278 |
| 242R | 22 | PB | AY | | 0-0 | 23-31-15 | SM00039 | | | | | | | | | D08150 | 1 | | | 280-299 |
| 243B | 22 | PB | BA | | 7-1 | 23-31-15 | SM00041 | | | | | | | | | SM00172 | | S | | 275-278 |
| 243R | 22 | PB | BA | | 0-0 | 23-31-15 | SM00042 | | | | | | | | | SM00173 | | S | | 275-278 |
| 244B | 22 | PB | BB | | 2-2 | 23-31-15 | SM00172 | | | | | | | | | D03248 | 2 | | | 150-199 |
| 244B | 22 | PB | BB | | 2-10 | 23-31-15 | SM00172 | | | | | | | | | D03248 | 2 | | | 275-278 |
| 244B | 22 | PB | BB | | 2-2 | 23-31-15 | SM00040 | | | | | | | | | D08152 | 2 | | | 280-299 |
| 244R | 22 | PB | BB | | 0-0 | 23-31-15 | SM00173 | | | | | | | | | D03248 | 1 | | | 150-199, 275-278 |
| 244R | 22 | PB | BB | | 0-0 | 23-31-15 | SM00039 | | | | | | | | | D08152 | 1 | | | 280-299 |
| 245B | 22 | PB | JT | | 6-10 | 23-31-15 | SM00044 | | | | | | | | | SM00048 | | S | | 280-299 |
| 245R | 22 | PB | JT | | 0-0 | 23-31-15 | SM00043 | | | | | | | | | SM00047 | | S | | 280-299 |
| 246B | 22 | PB | CA | | 1-8 | 23-31-15 | SM00108 | | | | | | | | | D03352 | 7 | | | 050-099 |
| 246B | 22 | PB | DI | | 2-0 | 23-31-15 | D03352 | | 7 | | | | | | | SM00153 | | S | | 150-199 |
| 246B | 22 | PB | JU | | 2-5 | 23-31-15 | SM00044 | | | | | | | | | D08154 | 2 | | | 280-299 |
| 246R | 22 | PB | CA | | 0-0 | 23-31-15 | SM00107 | | | | | | | | | D03352 | 6 | | | 050-099 |
| 246R | 22 | PB | DI | | 0-0 | 23-31-15 | D03352 | | 6 | | | | | | | SM00154 | | S | | 150-199 |
| 246R | 22 | PB | JU | | 0-0 | 23-31-15 | SM00043 | | | | | | | | | D08154 | 1 | | | 280-299 |
| 248B | 22 | PB | CC | | 2-2 | 23-31-15 | SM00108 | | | | | | | | | D03354 | 7 | | | 050-099 |
| 248B | 22 | PB | DJ | | 3-5 | 23-31-15 | D03354 | | 7 | | | | | | | SM00156 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 41

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | |
| 248B | 22 | PB | JW | | 2-9 | 23-31-15 | SM00044 | | S | | D03360 | | 2 | | 280-299 |
| 248R | 22 | PB | CC | | 0-0 | 23-31-15 | SM00107 | | S | | D03354 | | 6 | | 050-099 |
| 248R | 22 | PB | DJ | | 0-0 | 23-31-15 | D03354 | 6 | | | SM00155 | | | S | 150-199 |
| 248R | 22 | PB | JW | | 0-0 | 23-31-15 | SM00043 | | S | | D03360 | | 1 | | 280-299 |
| 249B | 22 | PB | BA | | 5-6 | 23-31-15 | SM00108 | | S | | SM00112 | | | S | 050-099 |
| 249B | 22 | PB | DK | | 5-9 | 23-31-15 | SM00156 | | S | | SM00158 | | | S | 150-199 |
| 249B | 22 | PB | JX | | 5-0 | 23-31-15 | SM00048 | | S | | SM00052 | | | S | 280-299 |
| 249R | 22 | PB | BA | | 0-0 | 23-31-15 | SM00107 | | S | | SM00111 | | | S | 050-099 |
| 249R | 22 | PB | DK | | 0-0 | 23-31-15 | SM00155 | | S | | SM00157 | | | S | 150-199 |
| 249R | 22 | PB | JX | | 0-0 | 23-31-15 | SM00047 | | S | | SM00051 | | | S | 280-299 |
| 250B | 22 | PB | BB | | 1-11 | 23-31-15 | SM00112 | | S | | D03356 | | 7 | | 050-099 |
| 250B | 22 | PB | DL | | 1-10 | 23-31-15 | D03356 | 7 | | | SM00156 | | | S | 150-199 |
| 250B | 22 | PB | JY | | 3-0 | 23-31-15 | SM00048 | | S | | D03362 | | 2 | | 280-299 |
| 250R | 22 | PB | BB | | 0-0 | 23-31-15 | SM00111 | | S | | D03356 | | 6 | | 050-099 |
| 250R | 22 | PB | DL | | 0-0 | 23-31-15 | D03356 | 6 | | | SM00155 | | | S | 150-199 |
| 250R | 22 | PB | JY | | 0-0 | 23-31-15 | SM00047 | | S | | D03362 | | 1 | | 280-299 |
| 251B | 22 | PB | DM | | 5-10 | 23-31-15 | SM00158 | | S | | SM00144 | | | S | 150-199 |
| 251R | 22 | PB | DM | | 0-0 | 23-31-15 | SM00157 | | S | | SM00143 | | | S | 150-199 |
| 252B | 22 | PB | BD | | 2-10 | 23-31-15 | SM00112 | | S | | D03358 | | 7 | | 050-099 |
| 252B | 22 | PB | BZ | | 2-9 | 23-31-15 | D03358 | 7 | | | SM00158 | | | S | 150-199 |
| 252B | 22 | PB | KB | | 1-6 | 23-31-15 | SM00048 | | S | | D03364 | | 2 | | 280-299 |
| 252R | 22 | PB | BD | | 0-0 | 23-31-15 | SM00111 | | S | | D03358 | | 6 | | 050-099 |
| 252R | 22 | PB | BZ | | 0-0 | 23-31-15 | D03358 | 6 | | | SM00157 | | | S | 150-199 |
| 252R | 22 | PB | KB | | 0-0 | 23-31-15 | SM00047 | | S | | D03364 | | 1 | | 280-299 |
| 253B | 22 | PB | BE | | 5-11 | 23-31-15 | SM00112 | | S | | SM00116 | | | S | 050-099 |
| 253B | 22 | PB | CD | | 3-6 | 23-31-15 | SM00144 | | S | | SM00114 | | | S | 150-199 |
| 253B | 22 | PB | KC | | 6-3 | 23-31-15 | SM00052 | | S | | SM00056 | | | S | 280-299 |
| 253R | 22 | PB | BE | | 0-0 | 23-31-15 | SM00111 | | S | | SM00115 | | | S | 050-099 |
| 253R | 22 | PB | CD | | 0-0 | 23-31-15 | SM00143 | | S | | SM00113 | | | S | 150-199 |
| 253R | 22 | PB | KC | | 0-0 | 23-31-15 | SM00051 | | S | | SM00055 | | | S | 280-299 |
| 254B | 22 | PB | BF | | 2-2 | 23-31-15 | SM00116 | | S | | D03360 | | 7 | | 050-099 |
| 254B | 22 | PB | CH | | 4-5 | 23-31-15 | D03360 | 7 | | | SM00114 | | | S | 150-199 |
| 254B | 22 | PB | KD | | 1-8 | 23-31-15 | SM00052 | | S | | D03366 | | 2 | | 280-299 |
| 254R | 22 | PB | BF | | 0-0 | 23-31-15 | SM00115 | | S | | D03360 | | 6 | | 050-099 |
| 254R | 22 | PB | CH | | 0-0 | 23-31-15 | D03360 | 6 | | | SM00113 | | | S | 150-199 |
| 254R | 22 | PB | KD | | 0-0 | 23-31-15 | SM00051 | | S | | D03366 | | 1 | | 280-299 |
| 255B | 22 | PB | DR | | 6-0 | 23-31-15 | SM00114 | | S | | SM00118 | | | S | 150-199 |
| 255R | 22 | PB | DR | | 0-0 | 23-31-15 | SM00113 | | S | | SM00117 | | | S | 150-199 |
| 256B | 22 | PB | BH | | 2-11 | 23-31-15 | SM00116 | | S | | D03362 | | 7 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 42

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | | |
| 256B | 22 | PB | DS | | 2-0 | 23-31-15 | D03362 | | 7 | | | SM00118 | | S | | 150-199 |
| 256B | 22 | PB | KF | | 3-2 | 23-31-15 | SM00052 | | | S | | D03368 | 2 | | | 280-299 |
| 256R | 22 | PB | BH | | 0-0 | 23-31-15 | SM00115 | | | S | | D03362 | 6 | | | 050-099 |
| 256R | 22 | PB | DS | | 0-0 | 23-31-15 | D03362 | | 6 | | | SM00117 | | S | | 150-199 |
| 256R | 22 | PB | KF | | 0-0 | 23-31-15 | SM00051 | | | S | | D03368 | 1 | | | 280-299 |
| 257B | 22 | PB | BI | | 6-2 | 23-31-15 | SM00116 | | | S | | SM00120 | | S | | 050-099 |
| 257B | 22 | PB | KG | | 4-8 | 23-31-15 | SM00056 | | | S | | SM00060 | | S | | 280-299 |
| 257R | 22 | PB | BI | | 0-0 | 23-31-15 | SM00115 | | | S | | SM00119 | | S | | 050-099 |
| 257R | 22 | PB | KG | | 0-0 | 23-31-15 | SM00055 | | | S | | SM00059 | | S | | 280-299 |
| 258B | 22 | PB | BJ | | 2-1 | 23-31-15 | SM00120 | | | S | | D03364 | 7 | | | 050-099 |
| 258B | 22 | PB | DT | | 4-1 | 23-31-15 | D03364 | | 7 | | | SM00118 | | S | | 150-199 |
| 258B | 22 | PB | KH | | 2-5 | 23-31-15 | SM00056 | | | S | | D03370 | 2 | | | 280-299 |
| 258R | 22 | PB | BJ | | 0-0 | 23-31-15 | SM00119 | | | S | | D03364 | 6 | | | 050-099 |
| 258R | 22 | PB | DT | | 0-0 | 23-31-15 | D03364 | | 6 | | | SM00117 | | S | | 150-199 |
| 258R | 22 | PB | KH | | 0-0 | 23-31-15 | SM00055 | | | S | | D03370 | 1 | | | 280-299 |
| 259B | 22 | PB | DU | | 5-11 | 23-31-15 | SM00118 | | | S | | SM00121 | | S | | 150-199 |
| 259R | 22 | PB | DU | | 0-0 | 23-31-15 | SM00117 | | | S | | SM00122 | | S | | 150-199 |
| 260B | 22 | PB | BL | | 2-6 | 23-31-15 | SM00120 | | | S | | D03366 | 7 | | | 050-099 |
| 260B | 22 | PB | CL | | 1-11 | 23-31-15 | D03366 | | 7 | | | SM00121 | | S | | 150-199 |
| 260B | 22 | PB | KJ | | 2-7 | 23-31-15 | SM00056 | | | S | | D03372 | 2 | | | 280-299 |
| 260R | 22 | PB | BL | | 0-0 | 23-31-15 | SM00119 | | | S | | D03366 | 6 | | | 050-099 |
| 260R | 22 | PB | CL | | 0-0 | 23-31-15 | D03366 | | 6 | | | SM00122 | | S | | 150-199 |
| 260R | 22 | PB | KJ | | 0-0 | 23-31-15 | SM00055 | | | S | | D03372 | 1 | | | 280-299 |
| 261B | 22 | PB | BM | | 5-8 | 23-31-15 | SM00120 | | | S | | SM00124 | | S | | 050-099 |
| 261R | 22 | PB | BM | | 0-0 | 23-31-15 | SM00119 | | | S | | SM00123 | | S | | 050-099 |
| 262B | 22 | PB | BN | | 2-1 | 23-31-15 | SM00124 | | | S | | D03368 | 7 | | | 050-099 |
| 262B | 22 | PB | DV | | 4-4 | 23-31-15 | D03368 | | 7 | | | SM00121 | | S | | 150-199 |
| 262B | 22 | PB | KL | | 1-11 | 23-31-15 | SM00060 | | | S | | D03374 | 2 | | | 280-299 |
| 262R | 22 | PB | BN | | 0-0 | 23-31-15 | SM00123 | | | S | | D03368 | 6 | | | 050-099 |
| 262R | 22 | PB | DV | | 0-0 | 23-31-15 | D03368 | | 6 | | | SM00122 | | S | | 150-199 |
| 262R | 22 | PB | KL | | 0-0 | 23-31-15 | SM00059 | | | S | | D03374 | 1 | | | 280-299 |
| 263B | 22 | PB | DX | | 5-10 | 23-31-15 | SM00121 | | | S | | SM00125 | | S | | 150-199 |
| 263R | 22 | PB | DX | | 0-0 | 23-31-15 | SM00122 | | | S | | SM00126 | | S | | 150-199 |
| 264B | 22 | PB | BQ | | 2-8 | 23-31-15 | SM00124 | | | S | | D03370 | 7 | | | 050-099 |
| 264B | 22 | PB | CP | | 1-8 | 23-31-15 | D03370 | | 7 | | | SM00125 | | S | | 150-199 |
| 264B | 22 | PB | KN | | 3-3 | 23-31-15 | SM00060 | | | S | | D03376 | 2 | | | 280-299 |
| 264R | 22 | PB | BQ | | 0-0 | 23-31-15 | SM00123 | | | S | | D03370 | 6 | | | 050-099 |
| 264R | 22 | PB | CP | | 0-0 | 23-31-15 | D03370 | | 6 | | | SM00126 | | S | | 150-199 |
| 264R | 22 | PB | KN | | 0-0 | 23-31-15 | SM00059 | | | S | | D03376 | 1 | | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 43

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | |
| 265B | 22 | PB | BR | | 5-9 | 23-31-15 | SM00124 | | S | | SM00128 | | S | | 050-099 |
| 265R | 22 | PB | BR | | 0-0 | 23-31-15 | SM00123 | | S | | SM00127 | | S | | 050-099 |
| 266B | 22 | PB | BS | | 1-10 | 23-31-15 | SM00128 | | S | | D03372 | 7 | | | 050-099 |
| 266B | 22 | PB | DY | | 4-3 | 23-31-15 | D03372 | 7 | | | SM00125 | | S | | 150-199 |
| 266R | 22 | PB | BS | | 0-0 | 23-31-15 | SM00127 | | S | | D03372 | 6 | | | 050-099 |
| 266R | 22 | PB | DY | | 0-0 | 23-31-15 | D03372 | 6 | | | SM00126 | | S | | 150-199 |
| 267B | 22 | PB | DZ | | 5-9 | 23-31-15 | SM00125 | | S | | SM00159 | | S | | 150-199 |
| 267R | 22 | PB | DZ | | 0-0 | 23-31-15 | SM00126 | | S | | SM00160 | | S | | 150-199 |
| 268B | 22 | PB | BU | | 3-1 | 23-31-15 | SM00127 | | S | | D03374 | 7 | | | 050-099 |
| 268B | 22 | PB | EC | | 2-0 | 23-31-15 | D03374 | 7 | | | SM00159 | | S | | 150-199 |
| 268R | 22 | PB | BU | | 0-0 | 23-31-15 | SM00128 | | S | | D03374 | 6 | | | 050-099 |
| 268R | 22 | PB | EC | | 0-0 | 23-31-15 | D03374 | 6 | | | SM00160 | | S | | 150-199 |
| 269B | 22 | PB | KS | | 4-8 | 23-31-15 | SM00132 | | S | | SM00128 | | S | | 050-099 |
| 269B | 22 | PB | ED | | 3-5 | 23-31-15 | D03376 | 7 | | | SM00159 | | S | | 150-199 |
| 269R | 22 | PB | KS | | 0-0 | 23-31-15 | SM00127 | | S | | SM00131 | | S | | 050-099 |
| 269R | 22 | PB | ED | | 0-0 | 23-31-15 | D03376 | 6 | | | SM00160 | | S | | 150-199 |
| 270B | 22 | PB | KT | | 1-5 | 23-31-15 | SM00132 | | S | | D03376 | 7 | | | 050-099 |
| 270R | 22 | PB | KT | | 0-0 | 23-31-15 | SM00131 | | S | | D03376 | 6 | | | 050-099 |
| 271B | 22 | PB | EF | | 5-4 | 23-31-15 | D12020 | 7 | | | SM00159 | | S | | 150-199 |
| 271R | 22 | PB | EF | | 0-0 | 23-31-15 | D12020 | 6 | | | SM00160 | | S | | 150-199 |
| 272B | 22 | PB | KV | | 2-8 | 23-31-15 | SM00132 | | S | | D12020 | 7 | | | 050-099 |
| 272R | 22 | PB | KV | | 0-0 | 23-31-15 | SM00131 | | S | | D12020 | 6 | | | 050-099 |
| 501 | 20 | PA | | | 2-0 | 33-24-12 | SM00124 | | S | | D03366 | 3 | | | 150-199 |
| 501 | 20 | PA | | | 1-8 | 33-24-12 | SM00124 | | S | | D03366 | 3 | | | 275-299 |
| 502 | 20 | PA | | | 2-0 | 33-24-12 | SM00123 | | S | | D03366 | 4 | | | 150-199 |
| 502 | 20 | PA | | | 1-8 | 33-24-12 | SM00123 | | S | | D03366 | 4 | | | 275-299 |
| 503 | 20 | PA | | | 4-3 | 33-24-12 | GD02164 | A.. | E | | D03366 | 5 | | | 150-199, 275-299 |
| 504 | 20 | PA | | | 2-10 | 33-24-12 | SM00124 | | S | | D03368 | 3 | | | 150-199 |
| 504 | 20 | PA | | | 3-2 | 33-24-12 | SM00124 | | S | | D03368 | 3 | | | 275-299 |
| 505 | 20 | PA | | | 2-10 | 33-24-12 | SM00123 | | S | | D03368 | 4 | | | 150-199 |
| 505 | 20 | PA | | | 3-2 | 33-24-12 | SM00123 | | S | | D03368 | 4 | | | 275-299 |
| 505B | 22 | PB | BN | | 3-9 | 23-31-15 | SM00171 | | S | | SM00030 | | S | | 150-199 |
| 505B | 22 | PB | BN | | 3-3 | 23-31-15 | SM00171 | | S | | SM00030 | | S | | 275-278 |
| 505R | 22 | PB | BN | | 0-0 | 23-31-15 | SM00170 | | S | | SM00029 | | S | | 150-199, 275-278 |
| 506 | 20 | PA | | | 1-11 | 33-24-12 | GD02164 | A.. | E | | D03368 | 5 | | | 150-199, 275-299 |
| 506B | 22 | PB | BO | | 1-10 | 23-31-15 | SM00171 | | S | | D08146 | 2 | | | 150-199 |
| 506B | 22 | PB | BO | | 2-11 | 23-31-15 | SM00171 | | S | | D08146 | 2 | | | 275-278 |
| 506R | 22 | PB | BO | | 0-0 | 23-31-15 | SM00170 | | S | | D08146 | 1 | | | 150-199, 275-278 |
| 507 | 20 | PA | | | 2-7 | 33-24-12 | SM00128 | | S | | D03370 | 3 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 44

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|-----|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | | | | |
| 507 | 20 | | PA | 2-10 | 33-24-12 | SM00128 | | | | | | | S | D03370 | 3 | | | 275-278 |
| 507 | 20 | | PA | 2-5 | 33-24-12 | SM00128 | | | | | | | S | D03370 | 3 | | | 280-299 |
| 508 | 20 | | PA | 2-7 | 33-24-12 | SM00127 | | | | | | | S | D03370 | 4 | | | 150-199 |
| 508 | 20 | | PA | 2-10 | 33-24-12 | SM00127 | | | | | | | S | D03370 | 4 | | | 275-278 |
| 508 | 20 | | PA | 2-5 | 33-24-12 | SM00127 | | | | | | | S | D03370 | 4 | | | 280-299 |
| 509 | 20 | | PA | 3-10 | 33-24-12 | GD02164 | | | | A.. | | | E | D03370 | 5 | | | 150-199 |
| 509 | 20 | | PA | 3-9 | 33-24-12 | GD02164 | | | | A.. | | | E | D03370 | 5 | | | 275-299 |
| 510 | 20 | | PA | 2-5 | 33-24-12 | SM00128 | | | | | | | S | D03372 | 3 | | | 150-199 |
| 510 | 20 | | PA | 5-5 | 33-24-12 | SM00128 | | | | | | | S | D03372 | 3 | | | 275-278 |
| 510 | 20 | | PA | 2-7 | 33-24-12 | SM00128 | | | | | | | S | D03372 | 3 | | | 280-299 |
| 511 | 20 | | PA | 2-5 | 33-24-12 | SM00127 | | | | | | | S | D03372 | 4 | | | 150-199 |
| 511 | 20 | | PA | 5-5 | 33-24-12 | SM00127 | | | | | | | S | D03372 | 4 | | | 275-278 |
| 511 | 20 | | PA | 2-7 | 33-24-12 | SM00127 | | | | | | | S | D03372 | 4 | | | 280-299 |
| 512 | 20 | | PA | 4-2 | 33-24-12 | GD02170 | | | | A.. | | | E | D03372 | 5 | | | 150-199 |
| 512 | 20 | | PA | 4-0 | 33-24-12 | GD02170 | | | | A.. | | | E | D03372 | 5 | | | 275-299 |
| 513 | 20 | | PA | 2-0 | 33-24-12 | SM00130 | | | | | | | S | D03374 | 3 | | | 150-199 |
| 513 | 20 | | PA | 1-11 | 33-24-12 | SM00130 | | | | | | | S | D03374 | 3 | | | 275-299 |
| 514 | 20 | | PA | 2-0 | 33-24-12 | SM00129 | | | | | | | S | D03374 | 4 | | | 150-199 |
| 514 | 20 | | PA | 1-11 | 33-24-12 | SM00129 | | | | | | | S | D03374 | 4 | | | 275-299 |
| 515 | 20 | | PA | 1-10 | 33-24-12 | GD02170 | | | | A.. | | | E | D03374 | 5 | | | 150-199, 275-299 |
| 516 | 20 | | PA | 3-5 | 33-24-12 | SM00130 | | | | | | | S | D03376 | 3 | | | 150-199 |
| 516 | 20 | | PA | 3-3 | 33-24-12 | SM00130 | | | | | | | S | D03376 | 3 | | | 275-299 |
| 517 | 20 | | PA | 3-5 | 33-24-12 | SM00129 | | | | | | | S | D03376 | 4 | | | 150-199 |
| 517 | 20 | | PA | 3-3 | 33-24-12 | SM00129 | | | | | | | S | D03376 | 4 | | | 275-299 |
| 518 | 20 | | PA | 3-3 | 33-24-12 | GD02170 | | | | A.. | | | E | D03376 | 5 | | | 150-199 |
| 518 | 20 | | PA | 3-2 | 33-24-12 | GD02170 | | | | A.. | | | E | D03376 | 5 | | | 275-299 |
| 522 | 22 | | PA | 4-11 | 33-24-12 | D12020 | | | | | 3 | | | SM00058 | | S | | 050-099 |
| 522 | 20 | | PA | 5-4 | 33-24-12 | D12020 | | | | | 3 | | | SM00130 | | S | | 150-199 |
| 523 | 22 | | PA | 4-11 | 33-24-12 | D12020 | | | | | 4 | | | SM00057 | | S | | 050-099 |
| 523 | 20 | | PA | 5-4 | 33-24-12 | D12020 | | | | | 4 | | | SM00129 | | S | | 150-199 |
| 524 | 20 | | PA | 4-9 | 33-24-12 | D12020 | | | | | 5 | | | GD02170 | | A.. | E | 050-099 |
| 524 | 20 | | PA | 5-2 | 33-24-12 | GD02170 | | | | A.. | | | E | D12020 | 5 | | | 150-199 |
| 601B | 22 | | PB | DE | 2-3 | 23-31-15 | SM00141 | | | | | | S | SM00101 | | S | | 150-199 |
| 601R | 22 | | PB | DE | 0-0 | 23-31-15 | SM00142 | | | | | | S | SM00102 | | S | | 150-199 |
| 602B | 22 | | PB | BR | 2-6 | 23-31-15 | D03348 | | | | 7 | | | SM00101 | | S | | 150-199 |
| 602R | 22 | | PB | BR | 0-0 | 23-31-15 | D03348 | | | | 6 | | | SM00102 | | S | | 150-199 |
| 603B | 22 | | PB | DG | 5-4 | 23-31-15 | SM00101 | | | | | | S | SM00153 | | S | | 150-199 |
| 603R | 22 | | PB | DG | 0-0 | 23-31-15 | SM00102 | | | | | | S | SM00154 | | S | | 150-199 |
| 604B | 22 | | PB | DH | 2-10 | 23-31-15 | D03350 | | | | 7 | | | SM00153 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 45

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | |
| 604R | 22 | PB | DH | | 0-0 | 23-31-15 | D03350 | | 6 | | SM00154 | | S | | 150-199 |
| 605B | 22 | PB | BV | | 6-1 | 23-31-15 | SM00153 | | | S | SM00156 | | S | | 150-199 |
| 605R | 22 | PB | BV | | 0-0 | 23-31-15 | SM00154 | | | S | SM00155 | | S | | 150-199 |
| 607B | 22 | PB | BP | | 5-4 | 23-31-15 | SM00172 | | | S | SM00176 | | S | | 150-199 |
| 607B | 22 | PB | BP | | 5-11 | 23-31-15 | SM00172 | | | S | SM00176 | | S | | 275-278 |
| 607R | 22 | PB | BP | | 0-0 | 23-31-15 | SM00173 | | | S | SM00177 | | S | | 150-199, 275-278 |
| 608B | 22 | PB | BQ | | 2-6 | 23-31-15 | SM00172 | | | S | D03348 | 2 | | | 150-199 |
| 608B | 22 | PB | BQ | | 1-8 | 23-31-15 | SM00172 | | | S | D03348 | 2 | | | 275-278 |
| 608R | 22 | PB | BQ | | 0-0 | 23-31-15 | SM00173 | | | S | D03348 | 1 | | | 150-199, 275-278 |
| 610B | 22 | PB | BS | | 2-10 | 23-31-15 | SM00176 | | | S | D03350 | 2 | | | 150-199, 275-278 |
| 610R | 22 | PB | BS | | 0-0 | 23-31-15 | SM00177 | | | S | D03350 | 1 | | | 150-199, 275-278 |
| 611B | 22 | PB | BT | | 6-1 | 23-31-15 | SM00176 | | | S | SM00181 | | S | | 150-199 |
| 611B | 22 | PB | BT | | 5-0 | 23-31-15 | SM00176 | | | S | SM00181 | | S | | 275-278 |
| 611R | 22 | PB | BT | | 0-0 | 23-31-15 | SM00177 | | | S | SM00180 | | S | | 150-199, 275-278 |
| 612B | 22 | PB | BU | | 2-0 | 23-31-15 | SM00176 | | | S | D03352 | 2 | | | 150-199, 275-278 |
| 612R | 22 | PB | BU | | 0-0 | 23-31-15 | SM00177 | | | S | D03352 | 1 | | | 150-199, 275-278 |
| 614B | 22 | PB | BW | | 3-5 | 23-31-15 | SM00181 | | | S | D03354 | 2 | | | 150-199 |
| 614B | 22 | PB | BW | | 2-0 | 23-31-15 | SM00181 | | | S | D03354 | 2 | | | 275-278 |
| 614R | 22 | PB | BW | | 0-0 | 23-31-15 | SM00180 | | | S | D03354 | 1 | | | 150-199, 275-278 |
| 615B | 22 | PB | BX | | 5-9 | 23-31-15 | SM00181 | | | S | SM00185 | | S | | 150-199 |
| 615B | 22 | PB | BX | | 7-1 | 23-31-15 | SM00181 | | | S | SM00185 | | S | | 275-278 |
| 615R | 22 | PB | BX | | 0-0 | 23-31-15 | SM00180 | | | S | SM00184 | | S | | 150-199, 275-278 |
| 616B | 22 | PB | BY | | 1-10 | 23-31-15 | SM00181 | | | S | D03356 | 2 | | | 150-199 |
| 616B | 22 | PB | BY | | 2-11 | 23-31-15 | SM00181 | | | S | D03356 | 2 | | | 275-278 |
| 616R | 22 | PB | BY | | 0-0 | 23-31-15 | SM00180 | | | S | D03356 | 1 | | | 150-199, 275-278 |
| 618B | 22 | PB | CA | | 2-9 | 23-31-15 | SM00185 | | | S | D03358 | 2 | | | 150-199 |
| 618B | 22 | PB | CA | | 3-1 | 23-31-15 | SM00185 | | | S | D03358 | 2 | | | 275-278 |
| 618R | 22 | PB | CA | | 0-0 | 23-31-15 | SM00184 | | | S | D03358 | 1 | | | 150-199, 275-278 |
| 619B | 22 | PB | CB | | 5-10 | 23-31-15 | SM00185 | | | S | SM00189 | | S | | 150-199, 275-278 |
| 619R | 22 | PB | CB | | 0-0 | 23-31-15 | SM00184 | | | S | SM00188 | | S | | 150-199, 275-278 |
| 620B | 22 | PB | CC | | 1-9 | 23-31-15 | SM00185 | | | S | D08148 | 2 | | | 150-199, 275-278 |
| 620R | 22 | PB | CC | | 0-0 | 23-31-15 | SM00184 | | | S | D08148 | 1 | | | 150-199, 275-278 |
| 622B | 22 | PB | CE | | 2-9 | 23-31-15 | SM00189 | | | S | D08150 | 2 | | | 150-199 |
| 622B | 22 | PB | CE | | 3-1 | 23-31-15 | SM00189 | | | S | D08150 | 2 | | | 275-278 |
| 622R | 22 | PB | CE | | 0-0 | 23-31-15 | SM00188 | | | S | D08150 | 1 | | | 150-199, 275-278 |
| 623B | 22 | PB | CF | | 4-7 | 23-31-15 | SM00189 | | | S | SM00193 | | S | | 150-199 |
| 623B | 22 | PB | CF | | 5-2 | 23-31-15 | SM00189 | | | S | SM00193 | | S | | 275-278 |
| 623R | 22 | PB | CF | | 0-0 | 23-31-15 | SM00188 | | | S | SM00192 | | S | | 150-199, 275-278 |
| 624B | 22 | PB | CG | | 2-2 | 23-31-15 | SM00189 | | | S | D08152 | 2 | | | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 46

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|------|------|--------|-------------|---|---|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | | | | | | |
| 624R | 22 | PB | CG | | 0-0 | 23-31-15 | SM00188 | | | | | | | | | D08152 | 1 | | | 150-199, 275-278 |
| 626B | 22 | PB | CI | | 1-10 | 23-31-15 | SM00193 | | | | | | | | | D08154 | 2 | | | 150-199 |
| 626B | 22 | PB | CI | | 2-5 | 23-31-15 | SM00193 | | | | | | | | | D08154 | 2 | | | 275-278 |
| 626R | 22 | PB | CI | | 0-0 | 23-31-15 | SM00192 | | | | | | | | | D08154 | 1 | | | 150-199, 275-278 |
| 627B | 22 | PB | CJ | | 7-3 | 23-31-15 | SM00193 | | | | | | | | | SM00196 | | S | | 150-199 |
| 627B | 22 | PB | CJ | | 6-10 | 23-31-15 | SM00193 | | | | | | | | | SM00196 | | S | | 275-278 |
| 627R | 22 | PB | CJ | | 0-0 | 23-31-15 | SM00192 | | | | | | | | | SM00197 | | S | | 150-199, 275-278 |
| 628B | 22 | PB | CK | | 3-4 | 23-31-15 | SM00193 | | | | | | | | | D03360 | 2 | | | 150-199 |
| 628B | 22 | PB | CK | | 2-9 | 23-31-15 | SM00193 | | | | | | | | | D03360 | 2 | | | 275-278 |
| 628R | 22 | PB | CK | | 0-0 | 23-31-15 | SM00192 | | | | | | | | | D03360 | 1 | | | 150-199, 275-278 |
| 630B | 22 | PB | CM | | 2-10 | 23-31-15 | SM00196 | | | | | | | | | D03362 | 2 | | | 150-199 |
| 630B | 22 | PB | CM | | 3-0 | 23-31-15 | SM00196 | | | | | | | | | D03362 | 2 | | | 275-278 |
| 630R | 22 | PB | CM | | 0-0 | 23-31-15 | SM00197 | | | | | | | | | D03362 | 1 | | | 150-199, 275-278 |
| 631B | 22 | PB | CN | | 5-1 | 23-31-15 | SM00196 | | | | | | | | | SM00202 | | S | | 150-199 |
| 631B | 22 | PB | CN | | 4-6 | 23-31-15 | SM00196 | | | | | | | | | SM00202 | | S | | 275-278 |
| 631R | 22 | PB | CN | | 0-0 | 23-31-15 | SM00197 | | | | | | | | | SM00203 | | S | | 150-199, 275-278 |
| 632B | 22 | PB | CO | | 1-9 | 23-31-15 | SM00196 | | | | | | | | | D03364 | 2 | | | 150-199 |
| 632B | 22 | PB | CO | | 1-6 | 23-31-15 | SM00196 | | | | | | | | | D03364 | 2 | | | 275-278 |
| 632R | 22 | PB | CO | | 0-0 | 23-31-15 | SM00197 | | | | | | | | | D03364 | 1 | | | 150-199, 275-278 |
| 634B | 22 | PB | CQ | | 2-0 | 23-31-15 | SM00202 | | | | | | | | | D03366 | 2 | | | 150-199 |
| 634B | 22 | PB | CQ | | 1-8 | 23-31-15 | SM00202 | | | | | | | | | D03366 | 2 | | | 275-278 |
| 634R | 22 | PB | CQ | | 0-0 | 23-31-15 | SM00203 | | | | | | | | | D03366 | 1 | | | 150-199, 275-278 |
| 635B | 22 | PB | CR | | 6-2 | 23-31-15 | SM00202 | | | | | | | | | SM00206 | | S | | 150-199 |
| 635B | 22 | PB | CR | | 3-5 | 23-31-15 | SM00202 | | | | | | | | | SM00206 | | S | | 275-278 |
| 635R | 22 | PB | CR | | 0-0 | 23-31-15 | SM00203 | | | | | | | | | SM00207 | | S | | 150-199, 275-278 |
| 636B | 22 | PB | CS | | 2-10 | 23-31-15 | SM00202 | | | | | | | | | D03368 | 2 | | | 150-199 |
| 636B | 22 | PB | CS | | 3-2 | 23-31-15 | SM00202 | | | | | | | | | D03368 | 2 | | | 275-278 |
| 636R | 22 | PB | CS | | 0-0 | 23-31-15 | SM00203 | | | | | | | | | D03368 | 1 | | | 150-199, 275-278 |
| 638B | 22 | PB | CU | | 2-7 | 23-31-15 | SM00206 | | | | | | | | | D03370 | 2 | | | 150-199 |
| 638B | 22 | PB | CU | | 2-10 | 23-31-15 | SM00206 | | | | | | | | | D03370 | 2 | | | 275-278 |
| 638R | 22 | PB | CU | | 0-0 | 23-31-15 | SM00207 | | | | | | | | | D03370 | 1 | | | 150-199, 275-278 |
| 639B | 22 | PB | CV | | 3-11 | 23-31-15 | SM00206 | | | | | | | | | SM00208 | | S | | 150-199 |
| 639B | 22 | PB | CV | | 7-1 | 23-31-15 | SM00206 | | | | | | | | | SM00208 | | S | | 275-278 |
| 639R | 22 | PB | CV | | 0-0 | 23-31-15 | SM00207 | | | | | | | | | SM00209 | | S | | 150-199, 275-278 |
| 640B | 22 | PB | CW | | 2-5 | 23-31-15 | SM00206 | | | | | | | | | D03372 | 2 | | | 150-199 |
| 640B | 22 | PB | CW | | 5-5 | 23-31-15 | SM00206 | | | | | | | | | D03372 | 2 | | | 275-278 |
| 640R | 22 | PB | CW | | 0-0 | 23-31-15 | SM00207 | | | | | | | | | D03372 | 1 | | | 150-199, 275-278 |
| 641B | 22 | PB | CX | | 3-5 | 23-31-15 | SM00208 | | | | | | | | | D03376 | 2 | | | 150-199 |
| 641B | 22 | PB | CX | | 3-3 | 23-31-15 | SM00208 | | | | | | | | | D03376 | 2 | | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 47

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | |
| 641R | 22 | PB | CX | | 0-0 | 23-31-15 | SM00209 | | | | | | | | 150-199, 275-278 |
| 642B | 22 | PB | CY | | 2-0 | 23-31-15 | SM00208 | | | | | | | | 150-199 |
| 642B | 22 | PB | CY | | 1-11 | 23-31-15 | SM00208 | | | | | | | | 275-278 |
| 642R | 22 | PB | CY | | 0-0 | 23-31-15 | SM00209 | | | | | | | | 150-199, 275-278 |
| 643B | 22 | PB | SS | | 5-4 | 23-31-15 | SM00212 | | | | | | | | 150-199 |
| 643R | 22 | PB | SS | | 0-0 | 23-31-15 | SM00213 | | | | | | | | 150-199 |
| 645B | 22 | PB | AV | | 1-1 | 23-31-15 | SM00208 | | | | | | | | 150-199 |
| 645R | 22 | PB | AV | | 0-0 | 23-31-15 | SM00209 | | | | | | | | 150-199 |
| 646B | 22 | PB | ZU | | 11-10 | 23-31-15 | SP01698 | | | | | | | | 050-099 |
| 646B | 22 | PB | BA | | 19-1 | 23-31-15 | SM00212 | | | | | | | | 150-199 |
| 646R | 22 | PB | ZU | | 0-0 | 23-31-15 | SP01696 | | | | | | | | 050-099 |
| 646R | 22 | PB | BA | | 0-0 | 23-31-15 | SM00213 | | | | | | | | 150-199 |
| 651B | 22 | PB | CZ | | 2-2 | 23-31-15 | D06514P | | 6 | | | | | | 150-199 |
| 651R | 22 | PB | CZ | | 0-0 | 23-31-15 | D06514P | | 5 | | | | | | 150-199 |
| 654B | 22 | PB | EA | | 1-10 | 23-31-15 | D08146 | | 7 | | | | | | 150-199 |
| 654R | 22 | PB | EA | | 0-0 | 23-31-15 | D08146 | | 6 | | | | | | 150-199 |
| 655B | 22 | PB | BF | | 3-9 | 23-31-15 | SM00133 | | | | | | | | 150-199 |
| 655R | 22 | PB | BF | | 0-0 | 23-31-15 | SM00134 | | | | | | | | 150-199 |
| 656B | 22 | PB | DB | | 1-11 | 23-31-15 | D03232 | | 7 | | | | | | 150-199 |
| 656R | 22 | PB | DB | | 0-0 | 23-31-15 | D03232 | | 6 | | | | | | 150-199 |
| 657B | 22 | PB | EB | | 6-8 | 23-31-15 | SM00135 | | | | | | | | 150-199 |
| 657R | 22 | PB | EB | | 0-0 | 23-31-15 | SM00136 | | | | | | | | 150-199 |
| 658B | 22 | PB | BG | | 3-2 | 23-31-15 | D03234 | | 7 | | | | | | 150-199 |
| 658R | 22 | PB | BG | | 0-0 | 23-31-15 | D03234 | | 6 | | | | | | 150-199 |
| 659B | 22 | PB | BI | | 14-11 | 23-31-15 | SM00137 | | | | | | | | 150-199 |
| 659R | 22 | PB | BI | | 0-0 | 23-31-15 | SM00138 | | | | | | | | 150-199 |
| 660B | 22 | PB | BH | | 2-9 | 23-31-15 | D03236 | | 7 | | | | | | 150-199 |
| 660R | 22 | PB | BH | | 0-0 | 23-31-15 | D03236 | | 6 | | | | | | 150-199 |
| 661B | 22 | PB | BM | | 7-8 | 23-31-15 | SM00139 | | | | | | | | 150-199 |
| 661R | 22 | PB | BM | | 0-0 | 23-31-15 | SM00140 | | | | | | | | 150-199 |
| 662B | 22 | PB | BJ | | 2-3 | 23-31-15 | D03238 | | 7 | | | | | | 150-199 |
| 662R | 22 | PB | BJ | | 0-0 | 23-31-15 | D03238 | | 6 | | | | | | 150-199 |
| 663B | 22 | PB | BK | | 12-2 | 23-31-15 | D03240 | | 7 | | | | | | 150-199 |
| 663R | 22 | PB | BK | | 0-0 | 23-31-15 | D03240 | | 6 | | | | | | 150-199 |
| 666B | 22 | PB | DD | | 2-9 | 23-31-15 | D03246 | | 7 | | | | | | 150-199 |
| 666R | 22 | PB | DD | | 0-0 | 23-31-15 | D03246 | | 6 | | | | | | 150-199 |
| 667B | 22 | PB | DF | | 2-2 | 23-31-15 | D03248 | | 7 | | | | | | 150-199 |
| 667R | 22 | PB | DF | | 0-0 | 23-31-15 | D03248 | | 6 | | | | | | 150-199 |
| 668B | 22 | PB | DN | | 1-9 | 23-31-15 | D08148 | | 7 | | | | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 48

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0806 | 286T0806 | | | SPEAKERS AND PASS SIGNS,AFT LEFT (continued) | | | | | | | | | | | | | |
| 668R | 22 | | PB | DN | 0-0 | 23-31-15 | D08148 | | 6 | | | | SM00157 | | S | | 150-199 |
| 669B | 22 | | PB | DO | 2-9 | 23-31-15 | D08150 | | 7 | | | | SM00144 | | S | | 150-199 |
| 669R | 22 | | PB | DO | 0-0 | 23-31-15 | D08150 | | 6 | | | | SM00143 | | S | | 150-199 |
| 670B | 22 | | PB | DP | 2-2 | 23-31-15 | D08152 | | 7 | | | | SM00144 | | S | | 150-199 |
| 670R | 22 | | PB | DP | 0-0 | 23-31-15 | D08152 | | 6 | | | | SM00143 | | S | | 150-199 |
| 671B | 22 | | PB | DQ | 1-9 | 23-31-15 | D08154 | | 7 | | | | SM00114 | | S | | 150-199 |
| 671R | 22 | | PB | DQ | 0-0 | 23-31-15 | D08154 | | 6 | | | | SM00113 | | S | | 150-199 |
| W0807 | 286T0807 | | | E2-2 TO ATC RF SWITCH | | | | | | | | | | | | | |
| 001 | 24 | | PK | | 8-0 | 34-53-13 | D06119J | | 1 | | | | D02187 | | A | | ALL |
| 002 | 24 | | PK | | 8-0 | 34-53-13 | D06119J | | 2 | | | | D02195 | | A | | ALL |
| 003 | 24 | | PK | | 8-0 | 34-53-13 | D06119J | | 3 | | | | D02187 | | C | | ALL |
| 004 | 24 | | PK | | 8-0 | 34-53-13 | D06119J | | 4 | | | | D02195 | | C | | ALL |
| 005 | 20 | | PA | | 3-0 | 34-53-13 | D02187 | | B | | | | GD00764 | D.. | E | | ALL |
| 006 | 20 | | PA | | 3-0 | 34-53-13 | D02195 | | B | | | | GD00764 | D.. | E | | ALL |
| W0809 | 286T0809 | | | SATCOM SYSTEM TOP-MOUNTED HGA SUBSYSTEM | | | | | | | | | | | | | |
| 002 | 20 | | PA | | 56-8 | 23-25-16 | D06165J | | 13 | | | | D02771 | | F | | 156-157, 166-199, 277-299 |
| 003 | 20 | | PA | | 55-10 | 23-25-16 | D06165J | | 14 | | | | D06167P | | 9 | | 156-157, 166-199, 277-299 |
| 004 | 20 | | PA | | 1-8 | 23-25-16 | D06167P | | 10 | | | | GD01906 | A.. | 2 | | 156-157, 166-199, 277-299 |
| 005 | 20 | | PA | | 1-8 | 23-25-16 | D06167P | | 11 | | | | GD01906 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 006 | 20 | | PA | | 1-8 | 23-25-16 | D06169J | | 10 | | | | GD06891 | S.. | E | | 156-157, 166-199, 277-299 |
| 007 | 20 | | PA | | 12-9 | 23-25-16 | D02771 | | E | | | | GD06891 | S.. | E | | 156-157, 166-199 |
| 007 | 20 | | PA | | 12-9 | 23-25-16 | D02771 | | E | | | | GD06893 | A.. | E | | 277-299 |
| 008 | 20 | | PA | | 12-8 | 23-25-16 | D02771 | | A | | | | GD06891 | S.. | E | | 156-157, 166-199 |
| 008 | 20 | | PA | | 12-8 | 23-25-16 | D02771 | | A | | | | GD06895 | S.. | E | | 277-299 |
| 201 | 20 | | UA | | 1-6 | 23-25-16 | D06169J | | REF | | IA | | GD06891 | S.. | E | | 156-157, 166-199, 277-299 |
| 201B | 24 | | PW | IA | 54-2 | 23-25-16 | D06165J | | 2 | | | | D06169J | | 2 | | 156-157, 166-199, 277-299 |
| 201R | 24 | | PW | IA | 0-0 | 23-25-16 | D06165J | | 1 | | | | D06169J | | 1 | | 156-157, 166-199, 277-299 |
| 201Z | | | | IA | 0-0 | 23-25-16 | D06165J | | 3 | | | | D06169J | REF | | IA | 156-157, 166-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 49

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0809 | 286T0809 | | | SATCOM SYSTEM TOP-MOUNTED HGA SUBSYSTEM (continued) | | | | | | | | | | | |
| 202 | 20 | | UA | 1-6 | 23-25-16 | D06169J | REF | | IB | GD06891 | S.. | E | *2 | 156-157, 166-199, 277-299 | |
| 202B | 24 | | PW | IB | 54-2 | 23-25-16 | D06165J | 5 | | D06169J | 5 | | | 156-157, 166-199, 277-299 | |
| 202R | 24 | | PW | IB | 0-0 | 23-25-16 | D06165J | 4 | | D06169J | 4 | | | 156-157, 166-199, 277-299 | |
| 202Z | | | | IB | 0-0 | 23-25-16 | D06165J | 6 | | D06169J | REF | | IB | 156-157, 166-199, 277-299 | |
| 203 | 20 | | UA | 1-6 | 23-25-16 | D06169J | REF | | IC | GD06891 | S.. | E | *2 | 156-157, 166-199, 277-299 | |
| 203B | 24 | | PW | IC | 54-2 | 23-25-16 | D06165J | 8 | | D06169J | 8 | | | 156-157, 166-199, 277-299 | |
| 203R | 24 | | PW | IC | 0-0 | 23-25-16 | D06165J | 7 | | D06169J | 7 | | | 156-157, 166-199, 277-299 | |
| 203Z | | | | IC | 0-0 | 23-25-16 | D06165J | 9 | | D06169J | REF | | IC | 156-157, 166-199, 277-299 | |
| 204B | 24 | | PL | ID | 55-10 | 23-25-16 | D06165J | 16 | | D06167P | 7 | | | 156-157, 166-199, 277-299 | |
| 204R | 24 | | PL | ID | 0-0 | 23-25-16 | D06165J | 15 | | D06167P | 8 | | | 156-157, 166-199, 277-299 | |
| 205 | 20 | | UA | 1-6 | 23-25-16 | D06167P | REF | | IE | GD01906 | S.. | 2 | | 156-157, 166-199, 277-299 | |
| 205B | 24 | | PW | IE | 55-10 | 23-25-16 | D06165J | 18 | | D06167P | 4 | | | 156-157, 166-199, 277-299 | |
| 205R | 24 | | PW | IE | 0-0 | 23-25-16 | D06165J | 17 | | D06167P | 5 | | | 156-157, 166-199, 277-299 | |
| 205Z | | | | IE | 0-0 | 23-25-16 | D06165J | 19 | | D06167P | REF | | IE | 156-157, 166-199, 277-299 | |
| 206 | 20 | | UA | 1-6 | 23-25-16 | D06167P | REF | | IF | GD01906 | S.. | 2 | | 156-157, 166-199, 277-299 | |
| 206B | 24 | | PW | IF | 55-10 | 23-25-16 | D06165J | 21 | | D06167P | 1 | | | 156-157, 166-199, 277-299 | |
| 206R | 24 | | PW | IF | 0-0 | 23-25-16 | D06165J | 20 | | D06167P | 2 | | | 156-157, 166-199, 277-299 | |
| 206Z | | | | IF | 0-0 | 23-25-16 | D06165J | 22 | | D06167P | REF | | IF | 156-157, 166-199, 277-299 | |
| 210B | 24 | | PL | IJ | 55-10 | 23-25-17 | D06165J | 23 | | D06167P | 12 | | | 156-157, 166-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W0800
Page 50
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-------|--|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0809 | 286T0809 | | | | SATCOM SYSTEM TOP-MOUNTED HGA SUBSYSTEM (continued) | | | | | | | | | | |
| 210R | 24 | PL | IJ | 0-0 | 23-25-17 | D06165J | 24 | | | | D06167P | 13 | | | 156-157, 166-199, 277-299 |
| 211B | 24 | PL | IK | 55-10 | 23-25-17 | D06165J | 26 | | | | D06167P | 15 | | | 156-157, 166-199, 277-299 |
| 211R | 24 | PL | IK | 0-0 | 23-25-17 | D06165J | 25 | | | | D06167P | 14 | | | 156-157, 166-199, 277-299 |
| 212 | 20 | UA | | 1-6 | 23-25-16 | GD06891 | S.. | E | *1 | | D06169J | REF | IL | | 156-157, 166-199, 277-299 |
| 212B | 24 | PW | IL | 54-2 | 23-25-16 | D06165J | 28 | | | | D06169J | 12 | | | 156-157, 166-199, 277-299 |
| 212R | 24 | PW | IL | 0-0 | 23-25-16 | D06165J | 27 | | | | D06169J | 11 | | | 156-157, 166-199, 277-299 |
| 212Z | | | IL | 0-0 | 23-25-16 | D06165J | 29 | | | | D06169J | REF | IL | | 156-157, 166-199, 277-299 |
| 213 | 20 | UA | | 1-6 | 23-25-16 | GD06891 | S.. | E | *1 | | D06169J | REF | IM | | 156-157, 166-199, 277-299 |
| 213B | 24 | PW | IM | 54-2 | 23-25-16 | D06165J | 31 | | | | D06169J | 15 | | | 156-157, 166-199, 277-299 |
| 213R | 24 | PW | IM | 0-0 | 23-25-16 | D06165J | 30 | | | | D06169J | 14 | | | 156-157, 166-199, 277-299 |
| 213Z | | | IM | 0-0 | 23-25-16 | D06165J | 32 | | | | D06169J | REF | IM | | 156-157, 166-199, 277-299 |
| 214B | 20 | PB | IN | 54-2 | 23-25-16 | D06165J | 34 | | | | D06169J | 18 | | | 156-157, 166-199, 277-299 |
| 214R | 20 | PB | IN | 0-0 | 23-25-16 | D06165J | 33 | | | | D06169J | 17 | | | 156-157, 166-199, 277-299 |
| 215B | 20 | PB | IO | 54-2 | 23-25-16 | D06165J | 36 | | | | D06169J | 20 | | | 156-157, 166-199, 277-299 |
| 215R | 20 | PB | IO | 0-0 | 23-25-16 | D06165J | 35 | | | | D06169J | 19 | | | 156-157, 166-199, 277-299 |
| 301B | 24 | PM | MA | 56-8 | 23-25-16 | D06165J | 12 | | | | D02771 | J | | | 156-157, 166-199, 277-299 |
| 301R | 24 | PM | MA | 0-0 | 23-25-16 | D06165J | 11 | | | | D02771 | H | | | 156-157, 166-199, 277-299 |
| 301Y | 24 | PM | MA | 0-0 | 23-25-16 | D06165J | 10 | | | | D02771 | B | | | 156-157, 166-199, 277-299 |
| FRA | | | | 0-0 | 23-25-16 | D06169J | REF | | IA | | D06169J | 3 | | | 156-157, 166-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0800

Page 51

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|---------|--------|-------|------|------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0809 | 286T0809 | | | SATCOM SYSTEM TOP-MOUNTED HGA SUBSYSTEM (continued) | | | | | | | | | | |
| FRB | | | | 0-0 | 23-25-16 | D06169J | REF | IB | D06169J | | 6 | | | 156-157, 166-199, 277-299 |
| FRC | | | | 0-0 | 23-25-16 | D06169J | REF | IC | D06169J | | 9 | | | 156-157, 166-199, 277-299 |
| FRE | | | | 0-0 | 23-25-16 | D06167P | REF | IE | D06167P | | 6 | | | 156-157, 166-199, 277-299 |
| FRF | | | | 0-0 | 23-25-16 | D06167P | REF | IF | D06167P | | 3 | | | 156-157, 166-199, 277-299 |
| FRL | | | | 0-0 | 23-25-16 | D06169J | | | D06169J | 13 | REF | | IL | 156-157, 166-199, 277-299 |
| FRM | | | | 0-0 | 23-25-16 | D06169J | | | D06169J | 16 | REF | | IM | 156-157, 166-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0800
Page 52 End
Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT | | | | | | | | | | | | | |
| 001 | 18 | | PA | 16-4 | 33-24-14 | D05108P | | 4 | | | | | SM00035 | | S | | 050-099 |
| 002 | 18 | | PA | 16-4 | 33-24-14 | D05108P | | 7 | | | | | SM00036 | | S | | 050-099 |
| 013 | 22 | | PA | 2-1 | 33-24-14 | SM00036 | | | | S | | | D03416 | 3 | | | 050-099 |
| 014 | 22 | | PA | 2-1 | 33-24-14 | SM00035 | | | | S | | | D03416 | 4 | | | 050-099 |
| 015 | 20 | | PA | 5-4 | 33-24-14 | GD01028 | | A.. | | E | | | D03416 | 5 | | | 050-099 |
| 016 | 18 | | PA | 6-1 | 33-24-14 | SM00035 | | | | S | | | SM00039 | | S | | 050-099 |
| 017 | 18 | | PA | 6-1 | 33-24-14 | SM00036 | | | | S | | | SM00040 | | S | | 050-099 |
| 018 | 22 | | PA | 2-10 | 33-24-14 | SM00040 | | | | S | | | D03418 | 3 | | | 050-099 |
| 019 | 22 | | PA | 2-10 | 33-24-14 | SM00039 | | | | S | | | D03418 | 4 | | | 050-099 |
| 020 | 20 | | PA | 4-2 | 33-24-14 | GD02354 | | A.. | | E | | | D03418 | 5 | | | 050-099 |
| 023 | 22 | | PA | 2-2 | 33-24-14 | SM00040 | | | | S | | | D03420 | 3 | | | 050-099 |
| 024 | 22 | | PA | 2-2 | 33-24-14 | SM00039 | | | | S | | | D03420 | 4 | | | 050-099 |
| 025 | 20 | | PA | 1-10 | 33-24-14 | GD02354 | | A.. | | E | | | D03420 | 5 | | | 050-099 |
| 026 | 18 | | PA | 5-7 | 33-24-14 | SM00039 | | | | S | | | SM00043 | | S | | 050-099 |
| 027 | 18 | | PA | 5-7 | 33-24-14 | SM00040 | | | | S | | | SM00044 | | S | | 050-099 |
| 028 | 22 | | PA | 1-11 | 33-24-14 | SM00044 | | | | S | | | D03422 | 3 | | | 050-099 |
| 029 | 22 | | PA | 1-11 | 33-24-14 | SM00043 | | | | S | | | D03422 | 4 | | | 050-099 |
| 030 | 20 | | PA | 3-7 | 33-24-14 | GD02354 | | A.. | | E | | | D03422 | 5 | | | 050-099 |
| 033 | 22 | | PA | 2-7 | 33-24-14 | SM00044 | | | | S | | | D03424 | 3 | | | 050-099 |
| 034 | 22 | | PA | 2-7 | 33-24-14 | SM00043 | | | | S | | | D03424 | 4 | | | 050-099 |
| 035 | 20 | | PA | 4-3 | 33-24-14 | GD02360 | | A.. | | E | | | D03424 | 5 | | | 050-099 |
| 036 | 18 | | PA | 7-0 | 33-24-14 | SM00043 | | | | S | | | SM00047 | | S | | 050-099 |
| 037 | 18 | | PA | 7-0 | 33-24-14 | SM00044 | | | | S | | | SM00048 | | S | | 050-099 |
| 038 | 22 | | PA | 2-11 | 33-24-14 | SM00048 | | | | S | | | D03426 | 3 | | | 050-099 |
| 039 | 22 | | PA | 2-11 | 33-24-14 | SM00047 | | | | S | | | D03426 | 4 | | | 050-099 |
| 040 | 20 | | PA | 1-7 | 33-24-14 | GD02360 | | A.. | | E | | | D03426 | 5 | | | 050-099 |
| 043 | 22 | | PA | 1-6 | 33-24-14 | SM00048 | | | | S | | | D03428 | 3 | | | 050-099 |
| 044 | 22 | | PA | 1-6 | 33-24-14 | SM00047 | | | | S | | | D03428 | 4 | | | 050-099 |
| 045 | 20 | | PA | 3-11 | 33-24-14 | GD02360 | | A.. | | E | | | D03428 | 5 | | | 050-099 |
| 046 | 18 | | PA | 6-3 | 33-24-14 | SM00047 | | | | S | | | SM00051 | | S | | 050-099 |
| 047 | 18 | | PA | 6-3 | 33-24-14 | SM00048 | | | | S | | | SM00052 | | S | | 050-099 |
| 048 | 22 | | PA | 3-0 | 33-24-14 | SM00052 | | | | S | | | D03430 | 3 | | | 050-099 |
| 049 | 22 | | PA | 3-0 | 33-24-14 | SM00051 | | | | S | | | D03430 | 4 | | | 050-099 |
| 050 | 20 | | PA | 4-2 | 33-24-14 | GD02366 | | A.. | | E | | | D03430 | 5 | | | 050-099 |
| 051 | 18 | | PA | 2-4 | 33-24-14 | D06516P | | 4 | | DL | | | SM00093 | | S | | 150-199 |
| 051 | 18 | | PA | 2-11 | 33-24-14 | D06516P | | 4 | | DL | | | SM00067 | | S | | 275-278 |
| 051 | 18 | | PA | 2-10 | 33-24-14 | D06516P | | 4 | | DL | | | SM00067 | | S | | 280-299 |
| 052 | 18 | | PA | 2-4 | 33-24-14 | D06516P | | 3 | | DL | | | SM00094 | | S | | 150-199 |
| 052 | 18 | | PA | 2-11 | 33-24-14 | D06516P | | 3 | | DL | | | SM00068 | | S | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | | | |
| 052 | 18 | PA | | 2-10 | 33-24-14 | D06516P | | 3 | DL | | | | SM00068 | | S | | 280-299 |
| 053 | 22 | PA | | 1-10 | 33-24-14 | SM00052 | | | S | | | | D03432 | 3 | | | 050-099 |
| 053 | 20 | PA | | 2-4 | 33-24-14 | SM00068 | | | S | | | | D03324 | 3 | | | 275-278 |
| 053 | 20 | PA | | 2-2 | 33-24-14 | SM00068 | | | S | | | | D03324 | 3 | | | 280-299 |
| 054 | 22 | PA | | 1-10 | 33-24-14 | SM00051 | | | S | | | | D03432 | 4 | | | 050-099 |
| 054 | 20 | PA | | 2-4 | 33-24-14 | SM00067 | | | S | | | | D03324 | 4 | | | 275-278 |
| 054 | 20 | PA | | 2-2 | 33-24-14 | SM00067 | | | S | | | | D03324 | 4 | | | 280-299 |
| 055 | 20 | PA | | 1-6 | 33-24-14 | GD02366 | | A.. | E | | | | D03432 | 5 | | | 050-099 |
| 055 | 20 | PA | | 4-6 | 33-24-14 | GD05044 | | A.. | E | | | | D03324 | 5 | | | 275-278 |
| 055 | 20 | PA | | 4-9 | 33-24-14 | GD05044 | | A.. | E | | | | D03324 | 5 | | | 280-299 |
| 056 | 18 | PA | | 4-4 | 33-24-14 | SM00051 | | | S | | | | SM00055 | | S | | 050-099 |
| 057 | 18 | PA | | 4-4 | 33-24-14 | SM00052 | | | S | | | | SM00056 | | S | | 050-099 |
| 058 | 22 | PA | | 1-6 | 33-24-14 | SM00056 | | | S | | | | D03434 | 3 | | | 050-099 |
| 058 | 20 | PA | | 2-8 | 33-24-14 | SM00068 | | | S | | | | D03326 | 3 | | | 275-278 |
| 058 | 20 | PA | | 2-6 | 33-24-14 | SM00068 | | | S | | | | D03326 | 3 | | | 280-299 |
| 059 | 22 | PA | | 1-6 | 33-24-14 | SM00055 | | | S | | | | D03434 | 4 | | | 050-099 |
| 059 | 20 | PA | | 2-8 | 33-24-14 | SM00067 | | | S | | | | D03326 | 4 | | | 275-278 |
| 059 | 20 | PA | | 2-6 | 33-24-14 | SM00067 | | | S | | | | D03326 | 4 | | | 280-299 |
| 060 | 20 | PA | | 3-11 | 33-24-14 | GD02366 | | A.. | E | | | | D03434 | 5 | | | 050-099 |
| 060 | 20 | PA | | 1-11 | 33-24-14 | GD05044 | | A.. | E | | | | D03326 | 5 | | | 275-278 |
| 060 | 20 | PA | | 2-7 | 33-24-14 | GD05044 | | A.. | E | | | | D03326 | 5 | | | 280-299 |
| 061 | 18 | PA | | 6-0 | 33-24-14 | SM00067 | | | S | | | | SM00093 | | S | | 275-278 |
| 061 | 18 | PA | | 6-2 | 33-24-14 | SM00067 | | | S | | | | SM00093 | | S | | 280-299 |
| 062 | 18 | PA | | 6-0 | 33-24-14 | SM00068 | | | S | | | | SM00094 | | S | | 275-278 |
| 062 | 18 | PA | | 6-2 | 33-24-14 | SM00068 | | | S | | | | SM00094 | | S | | 280-299 |
| 063 | 22 | PA | | 3-9 | 33-24-14 | SM00056 | | | S | | | | D03436 | 3 | | | 050-099 |
| 063 | 20 | PA | | 1-10 | 33-24-14 | SM00094 | | | S | | | | D03328 | 3 | | | 275-278 |
| 063 | 20 | PA | | 2-1 | 33-24-14 | SM00094 | | | S | | | | D03328 | 3 | | | 280-299 |
| 064 | 22 | PA | | 3-9 | 33-24-14 | SM00055 | | | S | | | | D03436 | 4 | | | 050-099 |
| 064 | 20 | PA | | 1-10 | 33-24-14 | SM00093 | | | S | | | | D03328 | 4 | | | 275-278 |
| 064 | 20 | PA | | 2-1 | 33-24-14 | SM00093 | | | S | | | | D03328 | 4 | | | 280-299 |
| 065 | 20 | PA | | 3-11 | 33-24-14 | GD02372 | | A.. | E | | | | D03436 | 5 | | | 050-099 |
| 065 | 20 | PA | | 3-11 | 33-24-14 | GD05044 | | A.. | E | | | | D03328 | 5 | | | 275-278 |
| 065 | 20 | PA | | 3-7 | 33-24-14 | GD05044 | | A.. | E | | | | D03328 | 5 | | | 280-299 |
| 066 | 18 | PA | | 3-9 | 33-24-14 | SM00055 | | | S | | | | SM00057 | | S | | 050-099 |
| 066 | 18 | PA | | 4-1 | 33-24-14 | SM00093 | | | S | | | | SM00073 | | S | | 150-199 |
| 066 | 18 | PA | | 6-3 | 33-24-14 | SM00093 | | | S | | | | SM00073 | | S | | 275-278 |
| 066 | 18 | PA | | 2-11 | 33-24-14 | SM00093 | | | S | | | | SM00073 | | S | | 280-299 |
| 067 | 18 | PA | | 3-9 | 33-24-14 | SM00056 | | | S | | | | SM00058 | | S | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | |
| 067 | 18 | | PA | | 4-1 | 33-24-14 | SM00094 | | | | SM00074 | | | | 150-199 |
| 067 | 18 | | PA | | 6-3 | 33-24-14 | SM00094 | | | | SM00074 | | | | 275-278 |
| 067 | 18 | | PA | | 2-11 | 33-24-14 | SM00094 | | | | SM00074 | | | | 280-299 |
| 068 | 22 | | PA | | 4-3 | 33-24-14 | SM00058 | | | | D03438 | 3 | | | 050-099 |
| 068 | 20 | | PA | | 2-0 | 33-24-14 | SM00074 | | | | D03330 | 3 | | | 150-199 |
| 068 | 20 | | PA | | 7-9 | 33-24-14 | SM00074 | | | | D03330 | 3 | | | 275-278 |
| 068 | 20 | | PA | | 3-7 | 33-24-14 | SM00074 | | | | D03330 | 3 | | | 280-299 |
| 069 | 22 | | PA | | 4-3 | 33-24-14 | SM00057 | | | | D03438 | 4 | | | 050-099 |
| 069 | 20 | | PA | | 2-0 | 33-24-14 | SM00073 | | | | D03330 | 4 | | | 150-199 |
| 069 | 20 | | PA | | 7-9 | 33-24-14 | SM00073 | | | | D03330 | 4 | | | 275-278 |
| 069 | 20 | | PA | | 3-7 | 33-24-14 | SM00073 | | | | D03330 | 4 | | | 280-299 |
| 070 | 20 | | PA | | 1-9 | 33-24-14 | GD02372 | | A.. | E | D03438 | 5 | | | 050-099 |
| 070 | 20 | | PA | | 1-11 | 33-24-14 | GD05636 | | A.. | E | D03330 | 5 | | | 150-199 |
| 070 | 20 | | PA | | 2-7 | 33-24-14 | GD05048 | | A.. | E | D03330 | 5 | | | 275-299 |
| 071 | 22 | | PA | | 6-0 | 33-24-14 | D03440 | | 4 | | SM00057 | | | S | 050-099 |
| 071 | 18 | | PA | | 6-5 | 33-24-14 | SM00073 | | | S | SM00077 | | | S | 150-199 |
| 072 | 22 | | PA | | 6-0 | 33-24-14 | D03440 | | 3 | | SM00058 | | | S | 050-099 |
| 072 | 18 | | PA | | 6-5 | 33-24-14 | SM00074 | | | S | SM00078 | | | S | 150-199 |
| 073 | 20 | | PA | | 2-10 | 33-24-14 | D03332 | | 3 | | SM00074 | | | S | 150-199 |
| 074 | 20 | | PA | | 2-10 | 33-24-14 | D03332 | | 4 | | SM00073 | | | S | 150-199 |
| 075 | 20 | | PA | | 3-0 | 33-24-14 | GD02372 | | A.. | E | D03440 | 5 | | | 050-099 |
| 075 | 20 | | PA | | 4-0 | 33-24-14 | D03332 | | 5 | | GD05636 | | A.. | E | 150-199 |
| 076 | 18 | | PA | | 21-3 | 33-24-14 | SM00073 | | | S | SM00077 | | | S | 275-278 |
| 076 | 18 | | PA | | 21-11 | 33-24-14 | SM00073 | | | S | SM00077 | | | S | 280-299 |
| 077 | 18 | | PA | | 21-3 | 33-24-14 | SM00074 | | | S | SM00078 | | | S | 275-278 |
| 077 | 18 | | PA | | 21-11 | 33-24-14 | SM00074 | | | S | SM00078 | | | S | 280-299 |
| 083 | 20 | | PA | | 2-7 | 33-24-14 | SM00078 | | | S | D03336 | 3 | | | 150-199 |
| 083 | 20 | | PA | | 1-2 | 33-24-14 | SM00078 | | | S | D03336 | 3 | | | 275-278 |
| 083 | 20 | | PA | | 6-0 | 33-24-14 | SM00078 | | | S | D03336 | 3 | | | 280-299 |
| 084 | 20 | | PA | | 2-7 | 33-24-14 | SM00077 | | | S | D03336 | 4 | | | 150-199 |
| 084 | 20 | | PA | | 1-2 | 33-24-14 | SM00077 | | | S | D03336 | 4 | | | 275-278 |
| 084 | 20 | | PA | | 6-0 | 33-24-14 | SM00077 | | | S | D03336 | 4 | | | 280-299 |
| 085 | 20 | | PA | | 4-9 | 33-24-14 | GD05138 | | A.. | E | D03336 | 5 | | | 150-199 |
| 085 | 20 | | PA | | 2-4 | 33-24-14 | GD05446 | | A.. | E | D03336 | 5 | | | 275-299 |
| 086 | 18 | | PA | | 4-1 | 33-24-14 | SM00077 | | | S | SM00081 | | | S | 150-199 |
| 086 | 18 | | PA | | 4-8 | 33-24-14 | SM00077 | | | S | SM00081 | | | S | 275-278 |
| 086 | 18 | | PA | | 3-4 | 33-24-14 | SM00077 | | | S | SM00081 | | | S | 280-299 |
| 087 | 18 | | PA | | 4-1 | 33-24-14 | SM00078 | | | S | SM00082 | | | S | 150-199 |
| 087 | 18 | | PA | | 4-8 | 33-24-14 | SM00078 | | | S | SM00082 | | | S | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | |
| 087 | 18 | | PA | | 3-4 | 33-24-14 | SM00078 | | S | | SM00082 | | S | | 280-299 |
| 088 | 20 | | PA | | 2-6 | 33-24-14 | SM00082 | | S | | D03338 | 3 | | | 150-199 |
| 088 | 20 | | PA | | 2-0 | 33-24-14 | SM00082 | | S | | D03338 | 3 | | | 275-278 |
| 088 | 20 | | PA | | 3-9 | 33-24-14 | SM00082 | | S | | D03338 | 3 | | | 280-299 |
| 089 | 20 | | PA | | 2-6 | 33-24-14 | SM00081 | | S | | D03338 | 4 | | | 150-199 |
| 089 | 20 | | PA | | 2-0 | 33-24-14 | SM00081 | | S | | D03338 | 4 | | | 275-278 |
| 089 | 20 | | PA | | 3-9 | 33-24-14 | SM00081 | | S | | D03338 | 4 | | | 280-299 |
| 090 | 20 | | PA | | 2-2 | 33-24-14 | GD05138 | A.. | E | | D03338 | 5 | | | 150-199 |
| 090 | 20 | | PA | | 4-10 | 33-24-14 | GD05052 | A.. | E | | D03338 | 5 | | | 275-299 |
| 093 | 20 | | PA | | 2-4 | 33-24-14 | SM00082 | | S | | D03340 | 3 | | | 150-199 |
| 093 | 20 | | PA | | 2-9 | 33-24-14 | SM00082 | | S | | D03340 | 3 | | | 275-278 |
| 093 | 20 | | PA | | 1-6 | 33-24-14 | SM00082 | | S | | D03340 | 3 | | | 280-299 |
| 094 | 20 | | PA | | 2-4 | 33-24-14 | SM00081 | | S | | D03340 | 4 | | | 150-199 |
| 094 | 20 | | PA | | 2-9 | 33-24-14 | SM00081 | | S | | D03340 | 4 | | | 275-278 |
| 094 | 20 | | PA | | 1-6 | 33-24-14 | SM00081 | | S | | D03340 | 4 | | | 280-299 |
| 095 | 20 | | PA | | 3-10 | 33-24-14 | GD05138 | A.. | E | | D03340 | 5 | | | 150-199 |
| 095 | 20 | | PA | | 2-6 | 33-24-14 | GD05052 | A.. | E | | D03340 | 5 | | | 275-299 |
| 096 | 18 | | PA | | 18-11 | 33-24-14 | SM00081 | | S | | SM00085 | | S | | 150-199 |
| 096 | 18 | | PA | | 6-5 | 33-24-14 | SM00081 | | S | | SM00085 | | S | | 275-278 |
| 096 | 18 | | PA | | 5-2 | 33-24-14 | SM00081 | | S | | SM00085 | | S | | 280-299 |
| 097 | 18 | | PA | | 18-11 | 33-24-14 | SM00082 | | S | | SM00086 | | S | | 150-199 |
| 097 | 18 | | PA | | 6-5 | 33-24-14 | SM00082 | | S | | SM00086 | | S | | 275-278 |
| 097 | 18 | | PA | | 5-2 | 33-24-14 | SM00082 | | S | | SM00086 | | S | | 280-299 |
| 098 | 20 | | PA | | 2-4 | 33-24-14 | SM00086 | | S | | D03342 | 3 | | | 275-299 |
| 099 | 20 | | PA | | 2-4 | 33-24-14 | SM00085 | | S | | D03342 | 4 | | | 275-299 |
| 100 | 20 | | PA | | 4-0 | 33-24-14 | GD05052 | A.. | E | | D03342 | 5 | | | 275-278 |
| 100 | 20 | | PA | | 3-8 | 33-24-14 | GD05052 | A.. | E | | D03342 | 5 | | | 280-299 |
| 103 | 20 | | PA | | 2-1 | 33-24-14 | SM00086 | | S | | D03344 | 3 | | | 150-199 |
| 103 | 20 | | PA | | 3-0 | 33-24-14 | SM00086 | | S | | D03344 | 3 | | | 275-299 |
| 104 | 20 | | PA | | 2-1 | 33-24-14 | SM00085 | | S | | D03344 | 4 | | | 150-199 |
| 104 | 20 | | PA | | 3-0 | 33-24-14 | SM00085 | | S | | D03344 | 4 | | | 275-299 |
| 105 | 20 | | PA | | 1-11 | 33-24-14 | GD05638 | A.. | E | | D03344 | 5 | | | 150-199 |
| 105 | 20 | | PA | | 4-4 | 33-24-14 | GD05056 | A.. | E | | D03344 | 5 | | | 275-278 |
| 105 | 20 | | PA | | 4-7 | 33-24-14 | GD05056 | A.. | E | | D03344 | 5 | | | 280-299 |
| 106 | 18 | | PA | | 2-7 | 33-24-14 | SM00085 | | S | | SM00095 | | S | | 150-199 |
| 106 | 18 | | PA | | 6-11 | 33-24-14 | SM00085 | | S | | SM00095 | | S | | 275-299 |
| 107 | 18 | | PA | | 2-7 | 33-24-14 | SM00086 | | S | | SM00096 | | S | | 150-199 |
| 107 | 18 | | PA | | 6-11 | 33-24-14 | SM00086 | | S | | SM00096 | | S | | 275-299 |
| 108 | 20 | | PA | | 1-6 | 33-24-14 | SM00096 | | S | | D03346 | 3 | | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 4
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | | | |
| 108 | 20 | | PA | 3-3 | 33-24-14 | SM00096 | | | | | | S | D03346 | 3 | | | 275-278 |
| 108 | 20 | | PA | 2-11 | 33-24-14 | SM00096 | | | | | | S | D03346 | 3 | | | 280-299 |
| 109 | 20 | | PA | 1-6 | 33-24-14 | SM00095 | | | | | | S | D03346 | 4 | | | 150-199 |
| 109 | 20 | | PA | 3-3 | 33-24-14 | SM00095 | | | | | | S | D03346 | 4 | | | 275-278 |
| 109 | 20 | | PA | 2-11 | 33-24-14 | SM00095 | | | | | | S | D03346 | 4 | | | 280-299 |
| 110 | 20 | | PA | 3-4 | 33-24-14 | GD05640 | | | | | A.. | E | D03346 | 5 | | | 150-199 |
| 110 | 20 | | PA | 2-2 | 33-24-14 | GD05056 | | | | | A.. | E | D03346 | 5 | | | 275-299 |
| 120 | 20 | | PA | 4-8 | 33-24-14 | GD05636 | | | | | A.. | E | D08164 | 5 | | | 150-199 |
| 120 | 20 | | PA | 2-11 | 33-24-14 | GD05048 | | | | | A.. | E | D08164 | 5 | | | 275-278 |
| 120 | 20 | | PA | 3-2 | 33-24-14 | GD05048 | | | | | A.. | E | D08164 | 5 | | | 280-299 |
| 123 | 20 | | PA | 2-3 | 33-24-14 | SM00094 | | | | | | S | D08164 | 3 | | | 150-199 |
| 123 | 20 | | PA | 2-11 | 33-24-14 | SM00094 | | | | | | S | D08164 | 3 | | | 275-278 |
| 123 | 20 | | PA | 3-1 | 33-24-14 | SM00094 | | | | | | S | D08164 | 3 | | | 280-299 |
| 124 | 20 | | PA | 2-3 | 33-24-14 | SM00093 | | | | | | S | D08164 | 4 | | | 150-199 |
| 124 | 20 | | PA | 2-11 | 33-24-14 | SM00093 | | | | | | S | D08164 | 4 | | | 275-278 |
| 124 | 20 | | PA | 3-1 | 33-24-14 | SM00093 | | | | | | S | D08164 | 4 | | | 280-299 |
| 125 | 18 | | PA | 5-4 | 33-24-14 | SM00095 | | | | | | S | SM00099 | | S | | 150-199 |
| 125 | 18 | | PA | 5-1 | 33-24-14 | SM00095 | | | | | | S | SM00099 | | S | | 275-299 |
| 126 | 18 | | PA | 5-4 | 33-24-14 | SM00096 | | | | | | S | SM00100 | | S | | 150-199 |
| 126 | 18 | | PA | 5-1 | 33-24-14 | SM00096 | | | | | | S | SM00100 | | S | | 275-299 |
| 129 | 18 | | PA | 6-0 | 33-24-14 | SM00099 | | | | | | S | SM00103 | | S | | 150-199, 275-299 |
| 130 | 18 | | PA | 6-0 | 33-24-14 | SM00100 | | | | | | S | SM00104 | | S | | 150-199, 275-299 |
| 133 | 18 | | PA | 6-1 | 33-24-14 | SM00103 | | | | | | S | SM00107 | | S | | 150-199, 275-299 |
| 134 | 18 | | PA | 6-1 | 33-24-14 | SM00104 | | | | | | S | SM00108 | | S | | 150-199, 275-299 |
| 137 | 18 | | PA | 6-3 | 33-24-14 | SM00107 | | | | | | S | SM00111 | | S | | 150-199, 275-278 |
| 137 | 18 | | PA | 6-8 | 33-24-14 | SM00107 | | | | | | S | SM00111 | | S | | 280-299 |
| 138 | 18 | | PA | 6-3 | 33-24-14 | SM00108 | | | | | | S | SM00112 | | S | | 150-199, 275-278 |
| 138 | 18 | | PA | 6-8 | 33-24-14 | SM00108 | | | | | | S | SM00112 | | S | | 280-299 |
| 141 | 18 | | PA | 6-0 | 33-24-14 | SM00111 | | | | | | S | SM00115 | | S | | 150-199, 275-278 |
| 141 | 18 | | PA | 5-8 | 33-24-14 | SM00111 | | | | | | S | SM00115 | | S | | 280-299 |
| 142 | 18 | | PA | 6-0 | 33-24-14 | SM00112 | | | | | | S | SM00116 | | S | | 150-199, 275-278 |
| 142 | 18 | | PA | 5-8 | 33-24-14 | SM00112 | | | | | | S | SM00116 | | S | | 280-299 |
| 145 | 18 | | PA | 6-0 | 33-24-14 | SM00115 | | | | | | S | SM00119 | | S | | 150-199, 275-278 |
| 145 | 18 | | PA | 6-5 | 33-24-14 | SM00115 | | | | | | S | SM00119 | | S | | 280-299 |
| 146 | 18 | | PA | 6-0 | 33-24-14 | SM00116 | | | | | | S | SM00120 | | S | | 150-199, 275-278 |
| 146 | 18 | | PA | 6-5 | 33-24-14 | SM00116 | | | | | | S | SM00120 | | S | | 280-299 |
| 149 | 18 | | PA | 6-0 | 33-24-14 | SM00119 | | | | | | S | SM00123 | | S | | 150-199 |
| 149 | 18 | | PA | 6-4 | 33-24-14 | SM00119 | | | | | | S | SM00123 | | S | | 275-299 |
| 150 | 18 | | PA | 6-0 | 33-24-14 | SM00120 | | | | | | S | SM00124 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | | |
| 150 | 18 | PA | | | 6-4 | 33-24-14 | SM00120 | | | | S | SM00124 | | | S | 275-299 |
| 153 | 18 | PA | | | 6-2 | 33-24-14 | SM00123 | | | | S | SM00127 | | | S | 150-199, 275-299 |
| 154 | 18 | PA | | | 6-2 | 33-24-14 | SM00124 | | | | S | SM00128 | | | S | 150-199, 275-299 |
| 157 | 18 | PA | | | 6-5 | 33-24-14 | SM00127 | | | | S | SM00131 | | | S | 150-199, 275-299 |
| 158 | 18 | PA | | | 6-5 | 33-24-14 | SM00128 | | | | S | SM00132 | | | S | 150-199, 275-299 |
| 161 | 20 | PA | | | 3-2 | 33-24-14 | SM00096 | | | | S | D03412 | 3 | | | 150-199 |
| 161 | 20 | PA | | | 1-8 | 33-24-14 | SM00096 | | | | S | D03412 | 3 | | | 275-278 |
| 161 | 20 | PA | | | 1-9 | 33-24-14 | SM00096 | | | | S | D03412 | 3 | | | 280-299 |
| 162 | 20 | PA | | | 3-2 | 33-24-14 | SM00095 | | | | S | D03412 | 4 | | | 150-199 |
| 162 | 20 | PA | | | 1-8 | 33-24-14 | SM00095 | | | | S | D03412 | 4 | | | 275-278 |
| 162 | 20 | PA | | | 1-9 | 33-24-14 | SM00095 | | | | S | D03412 | 4 | | | 280-299 |
| 163 | 20 | PA | | | 2-5 | 33-24-14 | D03412 | | 5 | | | GD05640 | A.. | E | | 150-199 |
| 163 | 20 | PA | | | 4-1 | 33-24-14 | D03412 | | 5 | | | GD05056 | A.. | E | | 275-278 |
| 163 | 20 | PA | | | 3-9 | 33-24-14 | D03412 | | 5 | | | GD05056 | A.. | E | | 280-299 |
| 164 | 20 | PA | | | 2-0 | 33-24-14 | SM00100 | | | | S | D03414 | 3 | | | 150-199, 275-278 |
| 164 | 20 | PA | | | 1-8 | 33-24-14 | SM00100 | | | | S | D03414 | 3 | | | 280-299 |
| 165 | 20 | PA | | | 2-0 | 33-24-14 | SM00099 | | | | S | D03414 | 4 | | | 150-199, 275-278 |
| 165 | 20 | PA | | | 1-8 | 33-24-14 | SM00099 | | | | S | D03414 | 4 | | | 280-299 |
| 166 | 20 | PA | | | 4-8 | 33-24-14 | D03414 | | 5 | | | GD05060 | A.. | E | | 150-199, 275-278 |
| 166 | 20 | PA | | | 4-4 | 33-24-14 | D03414 | | 5 | | | GD05060 | A.. | E | | 280-299 |
| 167 | 20 | PA | | | 3-3 | 33-24-14 | SM00100 | | | | S | D03416 | 3 | | | 150-199, 275-299 |
| 168 | 20 | PA | | | 3-3 | 33-24-14 | SM00099 | | | | S | D03416 | 4 | | | 150-199, 275-299 |
| 169 | 20 | PA | | | 1-10 | 33-24-14 | D03416 | | 5 | | | GD05060 | A.. | E | | 150-199, 275-278 |
| 169 | 20 | PA | | | 1-9 | 33-24-14 | D03416 | | 5 | | | GD05060 | A.. | E | | 280-299 |
| 170 | 20 | PA | | | 1-10 | 33-24-14 | SM00104 | | | | S | D03418 | 3 | | | 150-199, 275-299 |
| 171 | 20 | PA | | | 1-10 | 33-24-14 | SM00103 | | | | S | D03418 | 4 | | | 150-199, 275-299 |
| 172 | 20 | PA | | | 3-10 | 33-24-14 | D03418 | | 5 | | | GD05060 | A.. | E | | 150-199, 275-299 |
| 173 | 20 | PA | | | 3-2 | 33-24-14 | SM00104 | | | | S | D03420 | 3 | | | 150-199, 275-299 |
| 174 | 20 | PA | | | 3-2 | 33-24-14 | SM00103 | | | | S | D03420 | 4 | | | 150-199, 275-299 |
| 175 | 20 | PA | | | 4-5 | 33-24-14 | D03420 | | 5 | | | GD05064 | A.. | E | | 150-199, 275-278 |
| 175 | 20 | PA | | | 4-4 | 33-24-14 | D03420 | | 5 | | | GD05064 | A.. | E | | 280-299 |
| 176 | 20 | PA | | | 1-10 | 33-24-14 | SM00108 | | | | S | D03422 | 3 | | | 150-199, 275-299 |
| 177 | 20 | PA | | | 1-10 | 33-24-14 | SM00107 | | | | S | D03422 | 4 | | | 150-199, 275-299 |
| 178 | 20 | PA | | | 1-11 | 33-24-14 | GD05064 | | | A.. | E | D03422 | 5 | | | 150-199, 275-299 |
| 179 | 20 | PA | | | 2-8 | 33-24-14 | SM00108 | | | | S | D08166 | 3 | | | 150-199, 275-299 |
| 180 | 20 | PA | | | 2-8 | 33-24-14 | SM00107 | | | | S | D08166 | 4 | | | 150-199, 275-299 |
| 181 | 20 | PA | | | 3-7 | 33-24-14 | GD05064 | | | A.. | E | D08166 | 5 | | | 150-199, 275-278 |
| 181 | 20 | PA | | | 3-6 | 33-24-14 | GD05064 | | | A.. | E | D08166 | 5 | | | 280-299 |
| 182 | 20 | PA | | | 1-9 | 33-24-14 | SM00112 | | | | S | D08168 | 3 | | | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | |
| 182 | 20 | | PA | | 2-7 | 33-24-14 | SM00112 | | S | | D08168 | 3 | | | 280-299 |
| 183 | 20 | | PA | | 1-9 | 33-24-14 | SM00111 | | S | | D08168 | 4 | | | 150-199, 275-278 |
| 183 | 20 | | PA | | 2-7 | 33-24-14 | SM00111 | | S | | D08168 | 4 | | | 280-299 |
| 184 | 20 | | PA | | 4-3 | 33-24-14 | GD05068 | A.. | E | | D08168 | 5 | | | 150-199, 275-299 |
| 185 | 20 | | PA | | 3-1 | 33-24-14 | SM00112 | | S | | D08170 | 3 | | | 150-199, 275-278 |
| 185 | 20 | | PA | | 2-3 | 33-24-14 | SM00112 | | S | | D08170 | 3 | | | 280-299 |
| 186 | 20 | | PA | | 3-1 | 33-24-14 | SM00111 | | S | | D08170 | 4 | | | 150-199, 275-278 |
| 186 | 20 | | PA | | 2-3 | 33-24-14 | SM00111 | | S | | D08170 | 4 | | | 280-299 |
| 187 | 20 | | PA | | 1-10 | 33-24-14 | GD05068 | A.. | E | | D08170 | 5 | | | 150-199, 275-299 |
| 188 | 20 | | PA | | 2-2 | 33-24-14 | SM00116 | | S | | D08172 | 3 | | | 150-199, 275-299 |
| 189 | 20 | | PA | | 2-2 | 33-24-14 | SM00115 | | S | | D08172 | 4 | | | 150-199, 275-299 |
| 190 | 20 | | PA | | 3-8 | 33-24-14 | GD05068 | A.. | E | | D08172 | 5 | | | 150-199, 275-299 |
| 191 | 20 | | PA | | 3-1 | 33-24-14 | SM00116 | | S | | D03424 | 3 | | | 150-199, 275-299 |
| 192 | 20 | | PA | | 3-1 | 33-24-14 | SM00115 | | S | | D03424 | 4 | | | 150-199, 275-299 |
| 193 | 20 | | PA | | 4-3 | 33-24-14 | D03424 | | 5 | | GD05072 | A.. | E | | 150-199, 275-278 |
| 193 | 20 | | PA | | 4-2 | 33-24-14 | D03424 | | 5 | | GD05072 | A.. | E | | 280-299 |
| 194 | 20 | | PA | | 1-10 | 33-24-14 | SM00120 | | S | | D03426 | 3 | | | 150-199, 275-278 |
| 194 | 20 | | PA | | 1-9 | 33-24-14 | SM00120 | | S | | D03426 | 3 | | | 280-299 |
| 195 | 20 | | PA | | 1-10 | 33-24-14 | SM00119 | | S | | D03426 | 4 | | | 150-199, 275-278 |
| 195 | 20 | | PA | | 1-9 | 33-24-14 | SM00119 | | S | | D03426 | 4 | | | 280-299 |
| 196 | 20 | | PA | | 1-9 | 33-24-14 | D03426 | | 5 | | GD05072 | A.. | E | | 150-199, 275-299 |
| 197 | 20 | | PA | | 2-11 | 33-24-14 | SM00120 | | S | | D03428 | 3 | | | 150-199, 275-278 |
| 197 | 20 | | PA | | 2-9 | 33-24-14 | SM00120 | | S | | D03428 | 3 | | | 280-299 |
| 198 | 20 | | PA | | 2-11 | 33-24-14 | SM00119 | | S | | D03428 | 4 | | | 150-199, 275-278 |
| 198 | 20 | | PA | | 2-9 | 33-24-14 | SM00119 | | S | | D03428 | 4 | | | 280-299 |
| 199 | 20 | | PA | | 3-11 | 33-24-14 | D03428 | | 5 | | GD05072 | A.. | E | | 150-199, 275-278 |
| 199 | 20 | | PA | | 3-9 | 33-24-14 | D03428 | | 5 | | GD05072 | A.. | E | | 280-299 |
| 201B | 22 | | PB | A | 18-8 | 23-31-17 | D05108P | | 2 | | SM00008 | | S | | 050-099 |
| 201B | 22 | | PB | IA | 2-10 | 23-31-17 | D06516P | | 2 | | SM00002 | | S | | 280-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-17 | D05108P | | 1 | | SM00007 | | S | | 050-099 |
| 201R | 22 | | PB | IA | 0-0 | 23-31-17 | D06516P | | 1 | | SM00001 | | S | | 280-299 |
| 202B | 22 | | PB | IB | 2-2 | 23-31-17 | D03324 | | 2 | | SM00002 | | S | | 280-299 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-17 | D03324 | | 1 | | SM00001 | | S | | 280-299 |
| 203B | 22 | | PB | IC | 6-2 | 23-31-17 | SM00002 | | S | | SM00004 | | S | | 280-299 |
| 203R | 22 | | PB | IC | 0-0 | 23-31-17 | SM00001 | | S | | SM00003 | | S | | 280-299 |
| 204B | 22 | | PB | ID | 2-6 | 23-31-17 | D03326 | | 2 | | SM00002 | | S | | 280-299 |
| 204R | 22 | | PB | ID | 0-0 | 23-31-17 | D03326 | | 1 | | SM00001 | | S | | 280-299 |
| 205B | 22 | | PB | IE | 2-11 | 23-31-17 | SM00004 | | S | | SM00008 | | S | | 280-299 |
| 205R | 22 | | PB | IE | 0-0 | 23-31-17 | SM00003 | | S | | SM00007 | | S | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | |
| 206B | 22 | PB | F | | 2-7 | 23-31-17 | SM00008 | | S | | D03416 | 2 | | | 050-099 |
| 206B | 22 | PB | IF | | 2-1 | 23-31-17 | D03328 | 2 | | | SM00004 | | S | | 280-299 |
| 206R | 22 | PB | F | | 0-0 | 23-31-17 | SM00007 | | S | | D03416 | 1 | | | 050-099 |
| 206R | 22 | PB | IF | | 0-0 | 23-31-17 | D03328 | 1 | | | SM00003 | | S | | 280-299 |
| 208B | 22 | PB | H | | 1-11 | 23-31-17 | SM00008 | | S | | D03418 | 2 | | | 050-099 |
| 208B | 22 | PB | IH | | 3-1 | 23-31-17 | D08164 | 2 | | | SM00004 | | S | | 280-299 |
| 208R | 22 | PB | H | | 0-0 | 23-31-17 | SM00007 | | S | | D03418 | 1 | | | 050-099 |
| 208R | 22 | PB | IH | | 0-0 | 23-31-17 | D08164 | 1 | | | SM00003 | | S | | 280-299 |
| 209B | 22 | PB | K | | 6-5 | 23-31-17 | SM00008 | | S | | SM00012 | | S | | 050-099 |
| 209B | 22 | PB | II | | 21-11 | 23-31-17 | SM00008 | | S | | SM00012 | | S | | 280-299 |
| 209R | 22 | PB | K | | 0-0 | 23-31-17 | SM00007 | | S | | SM00011 | | S | | 050-099 |
| 209R | 22 | PB | II | | 0-0 | 23-31-17 | SM00007 | | S | | SM00011 | | S | | 280-299 |
| 210B | 22 | PB | L | | 3-1 | 23-31-17 | SM00012 | | S | | D03420 | 2 | | | 050-099 |
| 210B | 22 | PB | IJ | | 3-7 | 23-31-17 | D03330 | 2 | | | SM00008 | | S | | 280-299 |
| 210R | 22 | PB | L | | 0-0 | 23-31-17 | SM00011 | | S | | D03420 | 1 | | | 050-099 |
| 210R | 22 | PB | IJ | | 0-0 | 23-31-17 | D03330 | 1 | | | SM00007 | | S | | 280-299 |
| 212B | 22 | PB | N | | 1-7 | 23-31-17 | SM00012 | | S | | D03422 | 2 | | | 050-099 |
| 212R | 22 | PB | N | | 0-0 | 23-31-17 | SM00011 | | S | | D03422 | 1 | | | 050-099 |
| 213B | 22 | PB | P | | 5-1 | 23-31-17 | SM00012 | | S | | SM00016 | | S | | 050-099 |
| 213B | 22 | PB | IM | | 3-4 | 23-31-17 | SM00012 | | S | | SM00016 | | S | | 280-299 |
| 213R | 22 | PB | P | | 0-0 | 23-31-17 | SM00011 | | S | | SM00015 | | S | | 050-099 |
| 213R | 22 | PB | IM | | 0-0 | 23-31-17 | SM00011 | | S | | SM00015 | | S | | 280-299 |
| 214B | 22 | PB | R | | 1-10 | 23-31-17 | SM00016 | | S | | D03424 | 2 | | | 050-099 |
| 214R | 22 | PB | R | | 0-0 | 23-31-17 | SM00015 | | S | | D03424 | 1 | | | 050-099 |
| 216B | 22 | PB | U | | 3-1 | 23-31-17 | SM00016 | | S | | D03426 | 2 | | | 050-099 |
| 216B | 22 | PB | IP | | 6-0 | 23-31-17 | SM00012 | | S | | D03336 | 2 | | | 280-299 |
| 216R | 22 | PB | U | | 0-0 | 23-31-17 | SM00015 | | S | | D03426 | 1 | | | 050-099 |
| 216R | 22 | PB | IP | | 0-0 | 23-31-17 | SM00011 | | S | | D03336 | 1 | | | 280-299 |
| 217B | 22 | PB | V | | 6-2 | 23-31-17 | SM00016 | | S | | SM00020 | | S | | 050-099 |
| 217B | 22 | PB | IQ | | 5-2 | 23-31-17 | SM00016 | | S | | SM00020 | | S | | 280-299 |
| 217R | 22 | PB | V | | 0-0 | 23-31-17 | SM00015 | | S | | SM00019 | | S | | 050-099 |
| 217R | 22 | PB | IQ | | 0-0 | 23-31-17 | SM00015 | | S | | SM00019 | | S | | 280-299 |
| 218B | 22 | PB | W | | 1-11 | 23-31-17 | SM00020 | | S | | D03428 | 2 | | | 050-099 |
| 218B | 22 | PB | IR | | 3-9 | 23-31-17 | SM00016 | | S | | D03338 | 2 | | | 280-299 |
| 218R | 22 | PB | W | | 0-0 | 23-31-17 | SM00019 | | S | | D03428 | 1 | | | 050-099 |
| 218R | 22 | PB | IR | | 0-0 | 23-31-17 | SM00015 | | S | | D03338 | 1 | | | 280-299 |
| 220B | 22 | PB | Y | | 2-7 | 23-31-17 | SM00020 | | S | | D03430 | 2 | | | 050-099 |
| 220B | 22 | PB | IT | | 1-6 | 23-31-17 | SM00016 | | S | | D03340 | 2 | | | 280-299 |
| 220R | 22 | PB | Y | | 0-0 | 23-31-17 | SM00019 | | S | | D03430 | 1 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | | |
| 220R | 22 | PB | IT | | 0-0 | 23-31-17 | SM00015 | | | S | | D03340 | 1 | | | 280-299 |
| 221B | 22 | PB | AA | | 6-5 | 23-31-17 | SM00020 | | | S | | SM00024 | | S | | 050-099 |
| 221B | 22 | PB | Y | | 2-4 | 23-31-17 | D06516P | | 2 | | | SM00171 | | S | | 150-199 |
| 221B | 22 | PB | Y | | 2-11 | 23-31-17 | D06516P | | 2 | | | SM00023 | | S | | 275-278 |
| 221B | 22 | PB | Y | | 6-11 | 23-31-17 | SM00020 | | | S | | SM00024 | | S | | 280-299 |
| 221R | 22 | PB | AA | | 0-0 | 23-31-17 | SM00019 | | | S | | SM00023 | | S | | 050-099 |
| 221R | 22 | PB | Y | | 0-0 | 23-31-17 | D06516P | | 1 | | | SM00170 | | S | | 150-199 |
| 221R | 22 | PB | Y | | 0-0 | 23-31-17 | D06516P | | 1 | | | SM00024 | | S | | 275-278 |
| 221R | 22 | PB | Y | | 0-0 | 23-31-17 | SM00019 | | | S | | SM00023 | | S | | 280-299 |
| 222B | 22 | PB | AB | | 1-7 | 23-31-17 | SM00024 | | | S | | D03432 | 2 | | | 050-099 |
| 222B | 22 | PB | AA | | 2-4 | 23-31-17 | SM00023 | | | S | | D03324 | 2 | | | 275-278 |
| 222B | 22 | PB | AA | | 2-4 | 23-31-17 | SM00020 | | | S | | D03342 | 2 | | | 280-299 |
| 222R | 22 | PB | AB | | 0-0 | 23-31-17 | SM00023 | | | S | | D03432 | 1 | | | 050-099 |
| 222R | 22 | PB | AA | | 0-0 | 23-31-17 | SM00024 | | | S | | D03324 | 1 | | | 275-278 |
| 222R | 22 | PB | AA | | 0-0 | 23-31-17 | SM00019 | | | S | | D03342 | 1 | | | 280-299 |
| 224B | 22 | PB | AD | | 2-10 | 23-31-17 | SM00024 | | | S | | D03434 | 2 | | | 050-099 |
| 224B | 22 | PB | AC | | 2-8 | 23-31-17 | SM00023 | | | S | | D03326 | 2 | | | 275-278 |
| 224B | 22 | PB | AC | | 3-0 | 23-31-17 | SM00020 | | | S | | D03344 | 2 | | | 280-299 |
| 224R | 22 | PB | AD | | 0-0 | 23-31-17 | SM00023 | | | S | | D03434 | 1 | | | 050-099 |
| 224R | 22 | PB | AC | | 0-0 | 23-31-17 | SM00024 | | | S | | D03326 | 1 | | | 275-278 |
| 224R | 22 | PB | AC | | 0-0 | 23-31-17 | SM00019 | | | S | | D03344 | 1 | | | 280-299 |
| 225B | 22 | PB | AE | | 5-2 | 23-31-17 | SM00024 | | | S | | SM00028 | | S | | 050-099 |
| 225B | 22 | PB | AD | | 6-0 | 23-31-17 | SM00023 | | | S | | SM00171 | | S | | 275-278 |
| 225B | 22 | PB | AD | | 5-1 | 23-31-17 | SM00024 | | | S | | SM00028 | | S | | 280-299 |
| 225R | 22 | PB | AE | | 0-0 | 23-31-17 | SM00023 | | | S | | SM00027 | | S | | 050-099 |
| 225R | 22 | PB | AD | | 0-0 | 23-31-17 | SM00024 | | | S | | SM00170 | | S | | 275-278 |
| 225R | 22 | PB | AD | | 0-0 | 23-31-17 | SM00023 | | | S | | SM00027 | | S | | 280-299 |
| 226B | 22 | PB | AF | | 1-7 | 23-31-17 | SM00028 | | | S | | D03436 | 2 | | | 050-099 |
| 226B | 22 | PB | AE | | 1-10 | 23-31-17 | SM00171 | | | S | | D03328 | 2 | | | 275-278 |
| 226B | 22 | PB | AE | | 2-11 | 23-31-17 | SM00024 | | | S | | D03346 | 2 | | | 280-299 |
| 226R | 22 | PB | AF | | 0-0 | 23-31-17 | SM00027 | | | S | | D03436 | 1 | | | 050-099 |
| 226R | 22 | PB | AE | | 0-0 | 23-31-17 | SM00170 | | | S | | D03328 | 1 | | | 275-278 |
| 226R | 22 | PB | AE | | 0-0 | 23-31-17 | SM00023 | | | S | | D03346 | 1 | | | 280-299 |
| 228B | 22 | PB | AH | | 4-3 | 23-31-17 | SM00028 | | | S | | D03438 | 2 | | | 050-099 |
| 228B | 22 | PB | AG | | 2-0 | 23-31-17 | SM00030 | | | S | | D03330 | 2 | | | 150-199 |
| 228B | 22 | PB | AG | | 7-9 | 23-31-17 | SM00030 | | | S | | D03330 | 2 | | | 275-278 |
| 228B | 22 | PB | AG | | 1-9 | 23-31-17 | SM00024 | | | S | | D03412 | 2 | | | 280-299 |
| 228R | 22 | PB | AH | | 0-0 | 23-31-17 | SM00027 | | | S | | D03438 | 1 | | | 050-099 |
| 228R | 22 | PB | AG | | 0-0 | 23-31-17 | SM00029 | | | S | | D03330 | 1 | | | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | |
| 228R | 22 | PB | AG | | 0-0 | 23-31-17 | SM00023 | | S | | D03412 | | 1 | | 280-299 |
| 229B | 22 | PB | JD | | 6-1 | 23-31-17 | SM00032 | | S | | SM00028 | | | S | 050-099 |
| 229B | 22 | PB | JD | | 6-0 | 23-31-17 | SM00028 | | S | | SM00032 | | | S | 280-299 |
| 229R | 22 | PB | JD | | 0-0 | 23-31-17 | SM00027 | | S | | SM00031 | | | S | 050-099, 280-299 |
| 230B | 22 | PB | AL | | 1-5 | 23-31-17 | SM00032 | | S | | D03440 | | 2 | | 050-099 |
| 230B | 22 | PB | AJ | | 2-10 | 23-31-17 | SM00030 | | S | | D03332 | | 2 | | 150-199 |
| 230B | 22 | PB | AJ | | 1-8 | 23-31-17 | SM00028 | | S | | D03414 | | 2 | | 280-299 |
| 230R | 22 | PB | AL | | 0-0 | 23-31-17 | SM00031 | | S | | D03440 | | 1 | | 050-099 |
| 230R | 22 | PB | AJ | | 0-0 | 23-31-17 | SM00029 | | S | | D03332 | | 1 | | 150-199 |
| 230R | 22 | PB | AJ | | 0-0 | 23-31-17 | SM00027 | | S | | D03414 | | 1 | | 280-299 |
| 231B | 22 | PB | AK | | 6-5 | 23-31-17 | SM00030 | | S | | SM00034 | | | S | 150-199 |
| 231B | 22 | PB | AK | | 21-3 | 23-31-17 | SM00030 | | S | | SM00034 | | | S | 275-278 |
| 231R | 22 | PB | AK | | 0-0 | 23-31-17 | SM00029 | | S | | SM00033 | | | S | 150-199, 275-278 |
| 232B | 22 | PB | JG | | 2-10 | 23-31-17 | SM00032 | | S | | D12022 | | 2 | | 050-099 |
| 232B | 22 | PB | AL | | 3-3 | 23-31-17 | SM00028 | | S | | D03416 | | 2 | | 280-299 |
| 232R | 22 | PB | JG | | 0-0 | 23-31-17 | SM00031 | | S | | D12022 | | 1 | | 050-099 |
| 232R | 22 | PB | AL | | 0-0 | 23-31-17 | SM00027 | | S | | D03416 | | 1 | | 280-299 |
| 233B | 22 | PB | JH | | 6-1 | 23-31-17 | SM00032 | | S | | SM00036 | | | S | 280-299 |
| 233R | 22 | PB | JH | | 0-0 | 23-31-17 | SM00031 | | S | | SM00035 | | | S | 280-299 |
| 234B | 22 | PB | AN | | 2-7 | 23-31-17 | SM00034 | | S | | D03336 | | 2 | | 150-199 |
| 234B | 22 | PB | AN | | 1-2 | 23-31-17 | SM00034 | | S | | D03336 | | 2 | | 275-278 |
| 234B | 22 | PB | AN | | 1-10 | 23-31-17 | SM00032 | | S | | D03418 | | 2 | | 280-299 |
| 234R | 22 | PB | AN | | 0-0 | 23-31-17 | SM00033 | | S | | D03336 | | 1 | | 150-199, 275-278 |
| 234R | 22 | PB | AN | | 0-0 | 23-31-17 | SM00031 | | S | | D03418 | | 1 | | 280-299 |
| 235B | 22 | PB | AP | | 4-8 | 23-31-17 | SM00034 | | S | | SM00038 | | | S | 275-278 |
| 235R | 22 | PB | AP | | 0-0 | 23-31-17 | SM00033 | | S | | SM00037 | | | S | 275-278 |
| 236B | 22 | PB | AR | | 2-6 | 23-31-17 | SM00034 | | S | | D03338 | | 2 | | 150-199 |
| 236B | 22 | PB | AR | | 2-0 | 23-31-17 | SM00038 | | S | | D03338 | | 2 | | 275-278 |
| 236B | 22 | PB | AR | | 3-2 | 23-31-17 | SM00032 | | S | | D03420 | | 2 | | 280-299 |
| 236R | 22 | PB | AR | | 0-0 | 23-31-17 | SM00033 | | S | | D03338 | | 1 | | 150-199 |
| 236R | 22 | PB | AR | | 0-0 | 23-31-17 | SM00037 | | S | | D03338 | | 1 | | 275-278 |
| 236R | 22 | PB | AR | | 0-0 | 23-31-17 | SM00031 | | S | | D03420 | | 1 | | 280-299 |
| 237B | 22 | PB | JL | | 6-8 | 23-31-17 | SM00036 | | S | | SM00040 | | | S | 280-299 |
| 237R | 22 | PB | JL | | 0-0 | 23-31-17 | SM00035 | | S | | SM00039 | | | S | 280-299 |
| 238B | 22 | PB | AU | | 4-10 | 23-31-17 | SM00034 | | S | | D03340 | | 2 | | 150-199 |
| 238B | 22 | PB | AU | | 2-9 | 23-31-17 | SM00038 | | S | | D03340 | | 2 | | 275-278 |
| 238B | 22 | PB | AU | | 1-10 | 23-31-17 | SM00036 | | S | | D03422 | | 2 | | 280-299 |
| 238R | 22 | PB | AU | | 0-0 | 23-31-17 | SM00033 | | S | | D03340 | | 1 | | 150-199 |
| 238R | 22 | PB | AU | | 0-0 | 23-31-17 | SM00037 | | S | | D03340 | | 1 | | 275-278 |

WIRE LIST

D280T132

91-21-11
 Section W0810
 Page 10
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | | |
| 238R | 22 | PB | AU | | 0-0 | 23-31-17 | SM00035 | | | S | | D03422 | 1 | | | 280-299 |
| 239B | 22 | PB | AV | | 6-5 | 23-31-17 | SM00038 | | | S | | SM00042 | | S | | 275-278 |
| 239R | 22 | PB | AV | | 0-0 | 23-31-17 | SM00037 | | | S | | SM00041 | | S | | 275-278 |
| 240B | 22 | PB | AW | | 2-4 | 23-31-17 | SM00042 | | | S | | D03342 | 2 | | | 275-278 |
| 240B | 22 | PB | AW | | 2-8 | 23-31-17 | SM00036 | | | S | | D08166 | 2 | | | 280-299 |
| 240R | 22 | PB | AW | | 0-0 | 23-31-17 | SM00041 | | | S | | D03342 | 1 | | | 275-278 |
| 240R | 22 | PB | AW | | 0-0 | 23-31-17 | SM00035 | | | S | | D08166 | 1 | | | 280-299 |
| 241B | 22 | PB | BA | | 18-8 | 23-31-17 | D05108P | | 5 | | | SM00108 | | S | | 050-099 |
| 241B | 22 | PB | JP | | 5-8 | 23-31-17 | SM00040 | | | S | | SM00044 | | S | | 280-299 |
| 241R | 22 | PB | BA | | 0-0 | 23-31-17 | D05108P | | 6 | | | SM00107 | | S | | 050-099 |
| 241R | 22 | PB | JP | | 0-0 | 23-31-17 | SM00039 | | | S | | SM00043 | | S | | 280-299 |
| 242B | 22 | PB | AY | | 3-2 | 23-31-17 | SM00172 | | | S | | D03344 | 2 | | | 150-199 |
| 242B | 22 | PB | AY | | 3-0 | 23-31-17 | SM00042 | | | S | | D03344 | 2 | | | 275-278 |
| 242B | 22 | PB | AY | | 2-7 | 23-31-17 | SM00040 | | | S | | D08168 | 2 | | | 280-299 |
| 242R | 22 | PB | AY | | 0-0 | 23-31-17 | SM00173 | | | S | | D03344 | 1 | | | 150-199 |
| 242R | 22 | PB | AY | | 0-0 | 23-31-17 | SM00041 | | | S | | D03344 | 1 | | | 275-278 |
| 242R | 22 | PB | AY | | 0-0 | 23-31-17 | SM00039 | | | S | | D08168 | 1 | | | 280-299 |
| 243B | 22 | PB | BA | | 6-11 | 23-31-17 | SM00042 | | | S | | SM00172 | | S | | 275-278 |
| 243R | 22 | PB | BA | | 0-0 | 23-31-17 | SM00041 | | | S | | SM00173 | | S | | 275-278 |
| 244B | 22 | PB | BB | | 1-6 | 23-31-17 | SM00172 | | | S | | D03346 | 2 | | | 150-199 |
| 244B | 22 | PB | BB | | 3-3 | 23-31-17 | SM00172 | | | S | | D03346 | 2 | | | 275-278 |
| 244B | 22 | PB | BB | | 2-3 | 23-31-17 | SM00040 | | | S | | D08170 | 2 | | | 280-299 |
| 244R | 22 | PB | BB | | 0-0 | 23-31-17 | SM00173 | | | S | | D03346 | 1 | | | 150-199, 275-278 |
| 244R | 22 | PB | BB | | 0-0 | 23-31-17 | SM00039 | | | S | | D08170 | 1 | | | 280-299 |
| 245B | 22 | PB | JT | | 6-5 | 23-31-17 | SM00044 | | | S | | SM00048 | | S | | 280-299 |
| 245R | 22 | PB | JT | | 0-0 | 23-31-17 | SM00043 | | | S | | SM00047 | | S | | 280-299 |
| 246B | 22 | PB | BO | | 2-7 | 23-31-17 | SM00108 | | | S | | D03416 | 7 | | | 050-099 |
| 246B | 22 | PB | DI | | 9-5 | 23-31-17 | SM00161 | | | S | | D03416 | 7 | | | 150-199 |
| 246B | 22 | PB | JU | | 2-2 | 23-31-17 | SM00044 | | | S | | D08172 | 2 | | | 280-299 |
| 246R | 22 | PB | BO | | 0-0 | 23-31-17 | SM00107 | | | S | | D03416 | 6 | | | 050-099 |
| 246R | 22 | PB | DI | | 0-0 | 23-31-17 | SM00199 | | | S | | D03416 | 6 | | | 150-199 |
| 246R | 22 | PB | JU | | 0-0 | 23-31-17 | SM00043 | | | S | | D08172 | 1 | | | 280-299 |
| 248B | 22 | PB | BQ | | 1-11 | 23-31-17 | SM00108 | | | S | | D03418 | 7 | | | 050-099 |
| 248B | 22 | PB | DJ | | 7-1 | 23-31-17 | SM00213 | | | S | | D03418 | 7 | | | 150-199 |
| 248B | 22 | PB | JW | | 3-1 | 23-31-17 | SM00044 | | | S | | D03424 | 2 | | | 280-299 |
| 248R | 22 | PB | BQ | | 0-0 | 23-31-17 | SM00107 | | | S | | D03418 | 6 | | | 050-099 |
| 248R | 22 | PB | DJ | | 0-0 | 23-31-17 | SM00211 | | | S | | D03418 | 6 | | | 150-199 |
| 248R | 22 | PB | JW | | 0-0 | 23-31-17 | SM00043 | | | S | | D03424 | 1 | | | 280-299 |
| 249B | 22 | PB | BR | | 6-5 | 23-31-17 | SM00108 | | | S | | SM00112 | | S | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | |
| 249B | 22 | PB | DK | 14-3 | 23-31-17 | SM00213 | | S | | SM00221 | | | S | | 150-199 |
| 249B | 22 | PB | JX | 6-4 | 23-31-17 | SM00048 | | S | | SM00052 | | | S | | 280-299 |
| 249R | 22 | PB | BR | 0-0 | 23-31-17 | SM00107 | | S | | SM00111 | | | S | | 050-099 |
| 249R | 22 | PB | DK | 0-0 | 23-31-17 | SM00211 | | S | | SM00219 | | | S | | 150-199 |
| 249R | 22 | PB | JX | 0-0 | 23-31-17 | SM00047 | | S | | SM00051 | | | S | | 280-299 |
| 250B | 22 | PB | BS | 3-1 | 23-31-17 | SM00112 | | S | | D03420 | | 7 | | | 050-099 |
| 250B | 22 | PB | DL | 0-24 | 23-31-17 | SM00213 | | S | | D03420 | | 7 | | | 150-199 |
| 250B | 22 | PB | JY | 1-9 | 23-31-17 | SM00048 | | S | | D03426 | | 2 | | | 280-299 |
| 250R | 22 | PB | BS | 0-0 | 23-31-17 | SM00111 | | S | | D03420 | | 6 | | | 050-099 |
| 250R | 22 | PB | DL | 0-0 | 23-31-17 | SM00211 | | S | | D03420 | | 6 | | | 150-199 |
| 250R | 22 | PB | JY | 0-0 | 23-31-17 | SM00047 | | S | | D03426 | | 1 | | | 280-299 |
| 251B | 22 | PB | DM | 4-2 | 23-31-17 | SM00221 | | S | | SM00144 | | | S | | 150-199 |
| 251R | 22 | PB | DM | 0-0 | 23-31-17 | SM00219 | | S | | SM00143 | | | S | | 150-199 |
| 252B | 22 | PB | BU | 1-7 | 23-31-17 | SM00112 | | S | | D03422 | | 7 | | | 050-099 |
| 252B | 22 | PB | BZ | 3-11 | 23-31-17 | SM00221 | | S | | D03422 | | 7 | | | 150-199 |
| 252B | 22 | PB | KB | 2-9 | 23-31-17 | SM00048 | | S | | D03428 | | 2 | | | 280-299 |
| 252R | 22 | PB | BU | 0-0 | 23-31-17 | SM00111 | | S | | D03422 | | 6 | | | 050-099 |
| 252R | 22 | PB | BZ | 0-0 | 23-31-17 | SM00219 | | S | | D03422 | | 6 | | | 150-199 |
| 252R | 22 | PB | KB | 0-0 | 23-31-17 | SM00047 | | S | | D03428 | | 1 | | | 280-299 |
| 253B | 22 | PB | BV | 5-1 | 23-31-17 | SM00112 | | S | | SM00116 | | | S | | 050-099 |
| 253B | 22 | PB | CD | 4-1 | 23-31-17 | SM00144 | | S | | SM00114 | | | S | | 150-199 |
| 253B | 22 | PB | KC | 6-2 | 23-31-17 | SM00052 | | S | | SM00056 | | | S | | 280-299 |
| 253R | 22 | PB | BV | 0-0 | 23-31-17 | SM00111 | | S | | SM00115 | | | S | | 050-099 |
| 253R | 22 | PB | CD | 0-0 | 23-31-17 | SM00143 | | S | | SM00113 | | | S | | 150-199 |
| 253R | 22 | PB | KC | 0-0 | 23-31-17 | SM00051 | | S | | SM00055 | | | S | | 280-299 |
| 254B | 22 | PB | BW | 1-10 | 23-31-17 | SM00116 | | S | | D03424 | | 7 | | | 050-099 |
| 254B | 22 | PB | CH | 6-0 | 23-31-17 | SM00114 | | S | | D03424 | | 7 | | | 150-199 |
| 254B | 22 | PB | KD | 1-9 | 23-31-17 | SM00052 | | S | | D03430 | | 2 | | | 280-299 |
| 254R | 22 | PB | BW | 0-0 | 23-31-17 | SM00115 | | S | | D03424 | | 6 | | | 050-099 |
| 254R | 22 | PB | CH | 0-0 | 23-31-17 | SM00113 | | S | | D03424 | | 6 | | | 150-199 |
| 254R | 22 | PB | KD | 0-0 | 23-31-17 | SM00051 | | S | | D03430 | | 1 | | | 280-299 |
| 255B | 22 | PB | DR | 6-5 | 23-31-17 | SM00114 | | S | | SM00118 | | | S | | 150-199 |
| 255R | 22 | PB | DR | 0-0 | 23-31-17 | SM00113 | | S | | SM00117 | | | S | | 150-199 |
| 256B | 22 | PB | BY | 3-1 | 23-31-17 | SM00116 | | S | | D03426 | | 7 | | | 050-099 |
| 256B | 22 | PB | DS | 3-1 | 23-31-17 | SM00118 | | S | | D03426 | | 7 | | | 150-199 |
| 256B | 22 | PB | KF | 3-1 | 23-31-17 | SM00052 | | S | | D03432 | | 2 | | | 280-299 |
| 256R | 22 | PB | BY | 0-0 | 23-31-17 | SM00115 | | S | | D03426 | | 6 | | | 050-099 |
| 256R | 22 | PB | DS | 0-0 | 23-31-17 | SM00117 | | S | | D03426 | | 6 | | | 150-199 |
| 256R | 22 | PB | KF | 0-0 | 23-31-17 | SM00051 | | S | | D03432 | | 1 | | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 12

Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | | |
| 257B | 22 | PB | BZ | | 6-2 | 23-31-17 | SM00116 | | | S | | SM00120 | | | S | 050-099 |
| 257B | 22 | PB | KG | | 6-5 | 23-31-17 | SM00056 | | | S | | SM00060 | | | S | 280-299 |
| 257R | 22 | PB | BZ | | 0-0 | 23-31-17 | SM00115 | | | S | | SM00119 | | | S | 050-099 |
| 257R | 22 | PB | KG | | 0-0 | 23-31-17 | SM00055 | | | S | | SM00059 | | | S | 280-299 |
| 258B | 22 | PB | CA | | 1-11 | 23-31-17 | SM00120 | | | S | | D03428 | 7 | | | 050-099 |
| 258B | 22 | PB | DT | | 5-4 | 23-31-17 | SM00118 | | | S | | D03428 | 7 | | | 150-199 |
| 258B | 22 | PB | KH | | 2-5 | 23-31-17 | SM00056 | | | S | | D03434 | 2 | | | 280-299 |
| 258R | 22 | PB | CA | | 0-0 | 23-31-17 | SM00119 | | | S | | D03428 | 6 | | | 050-099 |
| 258R | 22 | PB | DT | | 0-0 | 23-31-17 | SM00117 | | | S | | D03428 | 6 | | | 150-199 |
| 258R | 22 | PB | KH | | 0-0 | 23-31-17 | SM00055 | | | S | | D03434 | 1 | | | 280-299 |
| 259B | 22 | PB | DU | | 6-2 | 23-31-17 | SM00118 | | | S | | SM00121 | | | S | 150-199 |
| 259R | 22 | PB | DU | | 0-0 | 23-31-17 | SM00117 | | | S | | SM00122 | | | S | 150-199 |
| 260B | 22 | PB | CC | | 2-7 | 23-31-17 | SM00120 | | | S | | D03430 | 7 | | | 050-099 |
| 260B | 22 | PB | CL | | 2-11 | 23-31-17 | SM00121 | | | S | | D03430 | 7 | | | 150-199 |
| 260B | 22 | PB | KJ | | 2-8 | 23-31-17 | SM00056 | | | S | | D03436 | 2 | | | 280-299 |
| 260R | 22 | PB | CC | | 0-0 | 23-31-17 | SM00119 | | | S | | D03430 | 6 | | | 050-099 |
| 260R | 22 | PB | CL | | 0-0 | 23-31-17 | SM00122 | | | S | | D03430 | 6 | | | 150-199 |
| 260R | 22 | PB | KJ | | 0-0 | 23-31-17 | SM00055 | | | S | | D03436 | 1 | | | 280-299 |
| 261B | 22 | PB | BB | | 6-5 | 23-31-17 | SM00120 | | | S | | SM00124 | | | S | 050-099 |
| 261R | 22 | PB | BB | | 0-0 | 23-31-17 | SM00119 | | | S | | SM00123 | | | S | 050-099 |
| 262B | 22 | PB | BC | | 1-7 | 23-31-17 | SM00124 | | | S | | D03432 | 7 | | | 050-099 |
| 262B | 22 | PB | DV | | 5-5 | 23-31-17 | SM00121 | | | S | | D03432 | 7 | | | 150-199 |
| 262B | 22 | PB | KL | | 2-8 | 23-31-17 | SM00060 | | | S | | D03438 | 2 | | | 280-299 |
| 262R | 22 | PB | BC | | 0-0 | 23-31-17 | SM00123 | | | S | | D03432 | 6 | | | 050-099 |
| 262R | 22 | PB | DV | | 0-0 | 23-31-17 | SM00122 | | | S | | D03432 | 6 | | | 150-199 |
| 262R | 22 | PB | KL | | 0-0 | 23-31-17 | SM00059 | | | S | | D03438 | 1 | | | 280-299 |
| 263B | 22 | PB | DX | | 6-0 | 23-31-17 | SM00121 | | | S | | SM00125 | | | S | 150-199 |
| 263R | 22 | PB | DX | | 0-0 | 23-31-17 | SM00122 | | | S | | SM00126 | | | S | 150-199 |
| 264B | 22 | PB | BE | | 2-10 | 23-31-17 | SM00124 | | | S | | D03434 | 7 | | | 050-099 |
| 264B | 22 | PB | CP | | 2-6 | 23-31-17 | SM00125 | | | S | | D03434 | 7 | | | 150-199 |
| 264B | 22 | PB | KN | | 1-6 | 23-31-17 | SM00060 | | | S | | D03440 | 2 | | | 280-299 |
| 264R | 22 | PB | BE | | 0-0 | 23-31-17 | SM00123 | | | S | | D03434 | 6 | | | 050-099 |
| 264R | 22 | PB | CP | | 0-0 | 23-31-17 | SM00126 | | | S | | D03434 | 6 | | | 150-199 |
| 264R | 22 | PB | KN | | 0-0 | 23-31-17 | SM00059 | | | S | | D03440 | 1 | | | 280-299 |
| 265B | 22 | PB | BF | | 5-2 | 23-31-17 | SM00124 | | | S | | SM00128 | | | S | 050-099 |
| 265R | 22 | PB | BF | | 0-0 | 23-31-17 | SM00127 | | | S | | SM00123 | | | S | 050-099 |
| 266B | 22 | PB | BG | | 1-7 | 23-31-17 | SM00128 | | | S | | D03436 | 7 | | | 050-099 |
| 266B | 22 | PB | DY | | 5-2 | 23-31-17 | SM00125 | | | S | | D03436 | 7 | | | 150-199 |
| 266R | 22 | PB | BG | | 0-0 | 23-31-17 | SM00127 | | | S | | D03436 | 6 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | | |
| 266R | 22 | PB | DY | | 0-0 | 23-31-17 | SM00126 | | | | S | D03436 | 6 | | | 150-199 |
| 267B | 22 | PB | DZ | | 9-0 | 23-31-17 | SM00125 | | | | S | SM00215 | | S | | 150-199 |
| 267R | 22 | PB | DZ | | 0-0 | 23-31-17 | SM00126 | | | | S | SM00217 | | S | | 150-199 |
| 268B | 22 | PB | BI | | 4-3 | 23-31-17 | SM00128 | | | | S | D03438 | 7 | | | 050-099 |
| 268B | 22 | PB | EC | | 1-7 | 23-31-17 | SM00215 | | | | S | D03440 | 7 | | | 150-199 |
| 268R | 22 | PB | BI | | 0-0 | 23-31-17 | SM00127 | | | | S | D03438 | 6 | | | 050-099 |
| 268R | 22 | PB | EC | | 0-0 | 23-31-17 | SM00217 | | | | S | D03440 | 6 | | | 150-199 |
| 269B | 22 | PB | KS | | 6-1 | 23-31-17 | SM00128 | | | | S | SM00132 | | S | | 050-099 |
| 269B | 22 | PB | CT | | 2-9 | 23-31-17 | SM00215 | | | | S | D03438 | 7 | | | 150-199 |
| 269R | 22 | PB | KS | | 0-0 | 23-31-17 | SM00127 | | | | S | SM00131 | | S | | 050-099 |
| 269R | 22 | PB | CT | | 0-0 | 23-31-17 | SM00217 | | | | S | D03438 | 6 | | | 150-199 |
| 270B | 22 | PB | KT | | 1-5 | 23-31-17 | SM00132 | | | | S | D03440 | 7 | | | 050-099 |
| 270B | 22 | PB | CU | | 2-10 | 23-31-17 | SM00215 | | | | S | D12022 | 7 | | | 150-199 |
| 270R | 22 | PB | KT | | 0-0 | 23-31-17 | SM00131 | | | | S | D03440 | 6 | | | 050-099 |
| 270R | 22 | PB | CU | | 0-0 | 23-31-17 | SM00217 | | | | S | D12022 | 6 | | | 150-199 |
| 272B | 22 | PB | KV | | 2-10 | 23-31-17 | SM00132 | | | | S | D12022 | 7 | | | 050-099 |
| 272R | 22 | PB | KV | | 0-0 | 23-31-17 | SM00131 | | | | S | D12022 | 6 | | | 050-099 |
| 501 | 20 | PA | | | 1-10 | 33-24-14 | SM00124 | | | | S | D03430 | 3 | | | 150-199, 275-278 |
| 501 | 20 | PA | | | 1-9 | 33-24-14 | SM00124 | | | | S | D03430 | 3 | | | 280-299 |
| 502 | 20 | PA | | | 1-10 | 33-24-14 | SM00123 | | | | S | D03430 | 4 | | | 150-199, 275-278 |
| 502 | 20 | PA | | | 1-9 | 33-24-14 | SM00123 | | | | S | D03430 | 4 | | | 280-299 |
| 503 | 20 | PA | | | 4-3 | 33-24-14 | D03430 | | 5 | | | GD02366 | A.. | E | | 150-199, 275-299 |
| 504 | 20 | PA | | | 3-1 | 33-24-14 | SM00124 | | | | S | D03432 | 3 | | | 150-199, 275-299 |
| 505 | 20 | PA | | | 3-1 | 33-24-14 | SM00123 | | | | S | D03432 | 4 | | | 150-199, 275-299 |
| 505B | 22 | PB | BV | | 6-2 | 23-31-17 | SM00161 | | | | S | SM00213 | | S | | 150-199 |
| 505R | 22 | PB | BV | | 0-0 | 23-31-17 | SM00199 | | | | S | SM00211 | | S | | 150-199 |
| 506 | 20 | PA | | | 1-9 | 33-24-14 | D03432 | | 5 | | | GD02366 | A.. | E | | 150-199, 275-299 |
| 507 | 20 | PA | | | 2-5 | 33-24-14 | SM00128 | | | | S | D03434 | 3 | | | 150-199, 275-299 |
| 508 | 20 | PA | | | 2-5 | 33-24-14 | SM00127 | | | | S | D03434 | 4 | | | 150-199, 275-299 |
| 509 | 20 | PA | | | 3-8 | 33-24-14 | D03434 | | 5 | | | GD02366 | A.. | E | | 150-199, 275-299 |
| 510 | 20 | PA | | | 2-8 | 33-24-14 | SM00128 | | | | S | D03436 | 3 | | | 150-199, 275-299 |
| 511 | 20 | PA | | | 2-8 | 33-24-14 | SM00127 | | | | S | D03436 | 4 | | | 150-199, 275-299 |
| 512 | 20 | PA | | | 4-4 | 33-24-14 | D03436 | | 5 | | | GD02372 | A.. | E | | 150-199, 275-299 |
| 513 | 20 | PA | | | 2-9 | 33-24-14 | SM00132 | | | | S | D03438 | 3 | | | 150-199, 275-278 |
| 513 | 20 | PA | | | 2-8 | 33-24-14 | SM00132 | | | | S | D03438 | 3 | | | 280-299 |
| 514 | 20 | PA | | | 2-9 | 33-24-14 | SM00131 | | | | S | D03438 | 4 | | | 150-199, 275-278 |
| 514 | 20 | PA | | | 2-8 | 33-24-14 | SM00131 | | | | S | D03438 | 4 | | | 280-299 |
| 515 | 20 | PA | | | 1-11 | 33-24-14 | D03438 | | 5 | | | GD02372 | A.. | E | | 150-199, 275-278 |
| 515 | 20 | PA | | | 1-10 | 33-24-14 | D03438 | | 5 | | | GD02372 | A.. | E | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 14

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | | |
| 516 | 20 | | PA | 1-7 | 33-24-14 | SM00132 | | | | S | | | D03440 | 3 | | 150-199, 275-278 |
| 516 | 20 | | PA | 1-6 | 33-24-14 | SM00132 | | | | S | | | D03440 | 3 | | 280-299 |
| 517 | 20 | | PA | 1-7 | 33-24-14 | SM00131 | | | | S | | | D03440 | 4 | | 150-199, 275-278 |
| 517 | 20 | | PA | 1-6 | 33-24-14 | SM00131 | | | | S | | | D03440 | 4 | | 280-299 |
| 518 | 20 | | PA | 2-7 | 33-24-14 | D03440 | | | 5 | | | | GD02372 | A.. | E | 150-199, 275-299 |
| 521 | 18 | | PA | 10-11 | 33-24-14 | SM00131 | | | | S | | | SM00133 | | S | 150-199, 275-299 |
| 522 | 18 | | PA | 10-11 | 33-24-14 | SM00132 | | | | S | | | SM00134 | | S | 150-199, 275-299 |
| 525 | 20 | | PA | 3-7 | 33-24-14 | SM00133 | | | | S | | | L00416 | FSB | C | 150-157, 275-278 |
| 525 | 20 | | PA | 7-6 | 33-24-14 | SM00133 | | | | S | | | L00416 | FSB | C | 162-199 |
| 525 | 20 | | PA | 2-9 | 33-24-14 | SM00133 | | | | S | | | L00416 | FSB | C | 280-299 |
| 526 | 20 | | PA | 3-7 | 33-24-14 | SM00134 | | | | S | | | L00416 | NS | C | 150-157, 275-278 |
| 526 | 20 | | PA | 7-6 | 33-24-14 | SM00134 | | | | S | | | L00416 | NS | C | 162-199 |
| 526 | 20 | | PA | 2-9 | 33-24-14 | SM00134 | | | | S | | | L00416 | NS | C | 280-299 |
| 527 | 20 | | PA | 5-0 | 33-24-14 | L00416 | | | | GND | C | | GD00020 | A.. | 2 | 150-157, 275-278 |
| 527 | 20 | | PA | 10-10 | 33-24-14 | L00416 | | | | GND | C | | GD00020 | A.. | 2 | 162-199 |
| 527 | 20 | | PA | 5-1 | 33-24-14 | L00416 | | | | GND | C | | GD00020 | A.. | 2 | 280-299 |
| 528 | 20 | | PA | 18-3 | 33-24-12 | L00415 | | | | FSB | C | | SM00133 | | S | 150-157, 275-278 |
| 528 | 20 | | PA | 7-6 | 33-24-12 | L00415 | | | | FSB | C | | SM00133 | | S | 162-199 |
| 528 | 20 | | PA | 17-7 | 33-24-12 | L00415 | | | | FSB | C | | SM00133 | | S | 280-299 |
| 529 | 20 | | PA | 18-3 | 33-24-12 | L00415 | | | | NS | C | | SM00134 | | S | 150-157, 275-278 |
| 529 | 20 | | PA | 7-6 | 33-24-12 | L00415 | | | | NS | C | | SM00134 | | S | 162-199 |
| 529 | 20 | | PA | 17-7 | 33-24-12 | L00415 | | | | NS | C | | SM00134 | | S | 280-299 |
| 530 | 20 | | PA | 5-1 | 33-24-12 | L00415 | | | | GND | C | | GD00026 | A.. | 2 | 150-157, 275-278 |
| 530 | 20 | | PA | 10-10 | 33-24-12 | L00415 | | | | GND | C | | GD00020 | A.. | 2 | 162-199 |
| 530 | 20 | | PA | 4-9 | 33-24-12 | L00415 | | | | GND | C | | GD00026 | A.. | 2 | 280-299 |
| 531 | 20 | | PA | 20-8 | 33-24-13 | L00614 | | | | FSB | C | | SM00133 | | S | 275-278 |
| 531 | 20 | | PA | 20-9 | 33-24-13 | L00614 | | | | FSB | C | | SM00133 | | S | 280-299 |
| 532 | 20 | | PA | 20-8 | 33-24-13 | L00614 | | | | NS | C | | SM00134 | | S | 275-278 |
| 532 | 20 | | PA | 20-9 | 33-24-13 | L00614 | | | | NS | C | | SM00134 | | S | 280-299 |
| 533 | 20 | | PA | 23-11 | 33-24-13 | L00614 | | | | GND | C | | GD00020 | A.. | 2 | 275-278 |
| 533 | 20 | | PA | 23-10 | 33-24-13 | L00614 | | | | GND | C | | GD00020 | A.. | 2 | 280-299 |
| 555 | 22 | | PA | 7-10 | 33-24-14 | D12022 | | | | 4 | | | SM00057 | | S | 050-099 |
| 555 | 20 | | PA | 11-10 | 33-24-14 | D12022 | | | | 3 | | | SM00134 | | S | 150-199 |
| 556 | 22 | | PA | 7-10 | 33-24-14 | D12022 | | | | 3 | | | SM00058 | | S | 050-099 |
| 556 | 20 | | PA | 11-10 | 33-24-14 | D12022 | | | | 4 | | | SM00133 | | S | 150-199 |
| 557 | 20 | | PA | 4-11 | 33-24-14 | D12022 | | | | 5 | | | GD02372 | A.. | E | 050-099 |
| 557 | 20 | | PA | 4-8 | 33-24-14 | D12022 | | | | 5 | | | GD02372 | A.. | E | 150-199 |
| 601B | 22 | | PB | DE | 2-11 | 23-31-17 | SM00141 | | | | S | | SM00101 | | S | 150-199 |
| 601R | 22 | | PB | DE | 0-0 | 23-31-17 | SM00142 | | | | S | | SM00102 | | S | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | |
| 602B | 22 | PB | BR | | 2-11 | 23-31-17 | SM00101 | | S | | D03412 | 7 | | | 150-199 |
| 602R | 22 | PB | BR | | 0-0 | 23-31-17 | SM00102 | | S | | D03412 | 6 | | | 150-199 |
| 603B | 22 | PB | DG | | 7-5 | 23-31-17 | SM00101 | | S | | SM00161 | | S | | 150-199 |
| 603R | 22 | PB | DG | | 0-0 | 23-31-17 | SM00102 | | S | | SM00199 | | S | | 150-199 |
| 604B | 22 | PB | DH | | 6-11 | 23-31-17 | SM00161 | | S | | D03414 | 7 | | | 150-199 |
| 604R | 22 | PB | DH | | 0-0 | 23-31-17 | SM00199 | | S | | D03414 | 6 | | | 150-199 |
| 605B | 22 | PB | BN | | 4-1 | 23-31-17 | SM00171 | | S | | SM00030 | | S | | 150-199 |
| 605B | 22 | PB | BN | | 6-3 | 23-31-17 | SM00171 | | S | | SM00030 | | S | | 275-278 |
| 605R | 22 | PB | BN | | 0-0 | 23-31-17 | SM00170 | | S | | SM00029 | | S | | 150-199, 275-278 |
| 606B | 22 | PB | BO | | 2-3 | 23-31-17 | SM00171 | | S | | D08164 | 2 | | | 150-199 |
| 606B | 22 | PB | BO | | 2-11 | 23-31-17 | SM00171 | | S | | D08164 | 2 | | | 275-278 |
| 606R | 22 | PB | BO | | 0-0 | 23-31-17 | SM00170 | | S | | D08164 | 1 | | | 150-199, 275-278 |
| 607B | 22 | PB | BP | | 5-4 | 23-31-17 | SM00172 | | S | | SM00176 | | S | | 150-199 |
| 607B | 22 | PB | BP | | 5-1 | 23-31-17 | SM00172 | | S | | SM00176 | | S | | 275-278 |
| 607R | 22 | PB | BP | | 0-0 | 23-31-17 | SM00173 | | S | | SM00177 | | S | | 150-199, 275-278 |
| 608B | 22 | PB | BQ | | 3-2 | 23-31-17 | SM00172 | | S | | D03412 | 2 | | | 150-199 |
| 608B | 22 | PB | BQ | | 1-8 | 23-31-17 | SM00172 | | S | | D03412 | 2 | | | 275-278 |
| 608R | 22 | PB | BQ | | 0-0 | 23-31-17 | SM00173 | | S | | D03412 | 1 | | | 150-199, 275-278 |
| 610B | 22 | PB | BS | | 2-0 | 23-31-17 | SM00176 | | S | | D03414 | 2 | | | 150-199, 275-278 |
| 610R | 22 | PB | BS | | 0-0 | 23-31-17 | SM00177 | | S | | D03414 | 1 | | | 150-199, 275-278 |
| 611B | 22 | PB | BT | | 6-0 | 23-31-17 | SM00176 | | S | | SM00181 | | S | | 150-199, 275-278 |
| 611R | 22 | PB | BT | | 0-0 | 23-31-17 | SM00177 | | S | | SM00180 | | S | | 150-199, 275-278 |
| 612B | 22 | PB | BU | | 3-3 | 23-31-17 | SM00176 | | S | | D03416 | 2 | | | 150-199, 275-278 |
| 612R | 22 | PB | BU | | 0-0 | 23-31-17 | SM00177 | | S | | D03416 | 1 | | | 150-199, 275-278 |
| 614B | 22 | PB | BW | | 1-10 | 23-31-17 | SM00181 | | S | | D03418 | 2 | | | 150-199, 275-278 |
| 614R | 22 | PB | BW | | 0-0 | 23-31-17 | SM00180 | | S | | D03418 | 1 | | | 150-199, 275-278 |
| 615B | 22 | PB | BX | | 6-1 | 23-31-17 | SM00181 | | S | | SM00185 | | S | | 150-199, 275-278 |
| 615R | 22 | PB | BX | | 0-0 | 23-31-17 | SM00180 | | S | | SM00184 | | S | | 150-199, 275-278 |
| 616B | 22 | PB | BY | | 3-2 | 23-31-17 | SM00181 | | S | | D03420 | 2 | | | 150-199, 275-278 |
| 616R | 22 | PB | BY | | 0-0 | 23-31-17 | SM00180 | | S | | D03420 | 1 | | | 150-199, 275-278 |
| 618B | 22 | PB | CA | | 1-10 | 23-31-17 | SM00185 | | S | | D03422 | 2 | | | 150-199, 275-278 |
| 618R | 22 | PB | CA | | 0-0 | 23-31-17 | SM00184 | | S | | D03422 | 1 | | | 150-199, 275-278 |
| 619B | 22 | PB | CB | | 6-3 | 23-31-17 | SM00185 | | S | | SM00189 | | S | | 150-199, 275-278 |
| 619R | 22 | PB | CB | | 0-0 | 23-31-17 | SM00184 | | S | | SM00188 | | S | | 150-199, 275-278 |
| 620B | 22 | PB | CC | | 2-8 | 23-31-17 | SM00185 | | S | | D08166 | 2 | | | 150-199, 275-278 |
| 620R | 22 | PB | CC | | 0-0 | 23-31-17 | SM00184 | | S | | D08166 | 1 | | | 150-199, 275-278 |
| 622B | 22 | PB | CE | | 1-9 | 23-31-17 | SM00189 | | S | | D08168 | 2 | | | 150-199, 275-278 |
| 622R | 22 | PB | CE | | 0-0 | 23-31-17 | SM00188 | | S | | D08168 | 1 | | | 150-199, 275-278 |
| 623B | 22 | PB | CF | | 6-0 | 23-31-17 | SM00189 | | S | | SM00193 | | S | | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | | |
| 623R | 22 | PB | CF | | 0-0 | 23-31-17 | SM00188 | | | S | | | | | | 150-199, 275-278 |
| 624B | 22 | PB | CG | | 3-1 | 23-31-17 | SM00189 | | | S | | | 2 | | | 150-199, 275-278 |
| 624R | 22 | PB | CG | | 0-0 | 23-31-17 | SM00188 | | | S | | | 1 | | | 150-199, 275-278 |
| 626B | 22 | PB | CI | | 2-2 | 23-31-17 | SM00193 | | | S | | | 2 | | | 150-199, 275-278 |
| 626R | 22 | PB | CI | | 0-0 | 23-31-17 | SM00192 | | | S | | | 1 | | | 150-199, 275-278 |
| 627B | 22 | PB | CJ | | 6-0 | 23-31-17 | SM00193 | | | S | | | | | S | 150-199, 275-278 |
| 627R | 22 | PB | CJ | | 0-0 | 23-31-17 | SM00192 | | | S | | | | | S | 150-199, 275-278 |
| 628B | 22 | PB | CK | | 3-1 | 23-31-17 | SM00193 | | | S | | | 2 | | | 150-199, 275-278 |
| 628R | 22 | PB | CK | | 0-0 | 23-31-17 | SM00192 | | | S | | | 1 | | | 150-199, 275-278 |
| 630B | 22 | PB | CM | | 1-10 | 23-31-17 | SM00196 | | | S | | | 2 | | | 150-199, 275-278 |
| 630R | 22 | PB | CM | | 0-0 | 23-31-17 | SM00197 | | | S | | | 1 | | | 150-199, 275-278 |
| 631B | 22 | PB | CN | | 6-0 | 23-31-17 | SM00196 | | | S | | | | | S | 150-199 |
| 631B | 22 | PB | CN | | 6-4 | 23-31-17 | SM00196 | | | S | | | | | S | 275-278 |
| 631R | 22 | PB | CN | | 0-0 | 23-31-17 | SM00197 | | | S | | | | | S | 150-199, 275-278 |
| 632B | 22 | PB | CO | | 2-11 | 23-31-17 | SM00196 | | | S | | | 2 | | | 150-199, 275-278 |
| 632R | 22 | PB | CO | | 0-0 | 23-31-17 | SM00197 | | | S | | | 1 | | | 150-199, 275-278 |
| 634B | 22 | PB | CQ | | 1-10 | 23-31-17 | SM00202 | | | S | | | 2 | | | 150-199, 275-278 |
| 634R | 22 | PB | CQ | | 0-0 | 23-31-17 | SM00203 | | | S | | | 1 | | | 150-199, 275-278 |
| 635B | 22 | PB | CR | | 6-2 | 23-31-17 | SM00202 | | | S | | | | | S | 150-199, 275-278 |
| 635R | 22 | PB | CR | | 0-0 | 23-31-17 | SM00203 | | | S | | | | | S | 150-199, 275-278 |
| 636B | 22 | PB | CS | | 3-1 | 23-31-17 | SM00202 | | | S | | | 2 | | | 150-199, 275-278 |
| 636R | 22 | PB | CS | | 0-0 | 23-31-17 | SM00203 | | | S | | | 1 | | | 150-199, 275-278 |
| 638B | 22 | PB | JS | | 2-5 | 23-31-17 | SM00206 | | | S | | | 2 | | | 150-199 |
| 638B | 22 | PB | CU | | 2-5 | 23-31-17 | SM00206 | | | S | | | 2 | | | 275-278 |
| 638R | 22 | PB | JS | | 0-0 | 23-31-17 | SM00207 | | | S | | | 1 | | | 150-199 |
| 638R | 22 | PB | CU | | 0-0 | 23-31-17 | SM00207 | | | S | | | 1 | | | 275-278 |
| 639B | 22 | PB | CV | | 4-9 | 23-31-17 | SM00206 | | | S | | | | | S | 150-199, 275-278 |
| 639R | 22 | PB | CV | | 0-0 | 23-31-17 | SM00207 | | | S | | | | | S | 150-199, 275-278 |
| 640B | 22 | PB | CW | | 2-8 | 23-31-17 | SM00206 | | | S | | | 2 | | | 150-199, 275-278 |
| 640R | 22 | PB | CW | | 0-0 | 23-31-17 | SM00207 | | | S | | | 1 | | | 150-199, 275-278 |
| 641B | 22 | PB | CX | | 1-11 | 23-31-17 | SM00208 | | | S | | | 2 | | | 150-199, 275-278 |
| 641R | 22 | PB | CX | | 0-0 | 23-31-17 | SM00209 | | | S | | | 1 | | | 150-199, 275-278 |
| 642B | 22 | PB | CY | | 3-0 | 23-31-17 | SM00208 | | | S | | | 2 | | | 150-199, 275-278 |
| 642R | 22 | PB | CY | | 0-0 | 23-31-17 | SM00209 | | | S | | | 1 | | | 150-199, 275-278 |
| 643B | 22 | PB | JL | | 36-0 | 23-31-17 | SM00212 | | | S | | | 2 | | | 150-199 |
| 643R | 22 | PB | JL | | 0-0 | 23-31-17 | SM00225 | | | S | | | 1 | | | 150-199 |
| 645B | 22 | PB | BA | | 31-6 | 23-31-17 | SM00208 | | | S | | | | | S | 150-199 |
| 645R | 22 | PB | BA | | 0-0 | 23-31-17 | SM00209 | | | S | | | | | S | 150-199 |
| 646B | 22 | PB | ZU | | 19-9 | 23-31-17 | SM00032 | | | S | | | | | S | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 17

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | |
| 646B | 22 | PB | AV | | 52-11 | 23-31-17 | SM00212 | | S | | SP01698 | | S | | 150-199 |
| 646R | 22 | PB | ZU | | 0-0 | 23-31-17 | SM00031 | | S | | SP01696 | | S | | 050-099 |
| 646R | 22 | PB | AV | | 0-0 | 23-31-17 | SM00225 | | S | | SP01696 | | S | | 150-199 |
| 651B | 22 | PB | CZ | | 2-4 | 23-31-17 | D06516P | | 6 | | SM00159 | | S | | 150-199 |
| 651R | 22 | PB | CZ | | 0-0 | 23-31-17 | D06516P | | 5 | | SM00157 | | S | | 150-199 |
| 654B | 22 | PB | EA | | 2-3 | 23-31-17 | SM00159 | | S | | D08164 | 7 | | | 150-199 |
| 654R | 22 | PB | EA | | 0-0 | 23-31-17 | SM00157 | | S | | D08164 | 6 | | | 150-199 |
| 655B | 22 | PB | BF | | 4-1 | 23-31-17 | SM00159 | | S | | SM00135 | | S | | 150-199 |
| 655R | 22 | PB | BF | | 0-0 | 23-31-17 | SM00157 | | S | | SM00136 | | S | | 150-199 |
| 656B | 22 | PB | ED | | 2-0 | 23-31-17 | SM00135 | | S | | D03330 | 7 | | | 150-199 |
| 656R | 22 | PB | ED | | 0-0 | 23-31-17 | SM00136 | | S | | D03330 | 6 | | | 150-199 |
| 657B | 22 | PB | EB | | 6-5 | 23-31-17 | SM00135 | | S | | SM00137 | | S | | 150-199 |
| 657R | 22 | PB | EB | | 0-0 | 23-31-17 | SM00136 | | S | | SM00138 | | S | | 150-199 |
| 658B | 22 | PB | BG | | 2-10 | 23-31-17 | SM00135 | | S | | D03332 | 7 | | | 150-199 |
| 658R | 22 | PB | BG | | 0-0 | 23-31-17 | SM00136 | | S | | D03332 | 6 | | | 150-199 |
| 659B | 22 | PB | BI | | 4-1 | 23-31-17 | SM00137 | | S | | SM00139 | | S | | 150-199 |
| 659R | 22 | PB | BI | | 0-0 | 23-31-17 | SM00138 | | S | | SM00140 | | S | | 150-199 |
| 661B | 22 | PB | BM | | 18-11 | 23-31-17 | SM00139 | | S | | SM00141 | | S | | 150-199 |
| 661R | 22 | PB | BM | | 0-0 | 23-31-17 | SM00140 | | S | | SM00142 | | S | | 150-199 |
| 662B | 22 | PB | BJ | | 2-7 | 23-31-17 | SM00137 | | S | | D03336 | 7 | | | 150-199 |
| 662R | 22 | PB | BJ | | 0-0 | 23-31-17 | SM00138 | | S | | D03336 | 6 | | | 150-199 |
| 663B | 22 | PB | BK | | 2-6 | 23-31-17 | SM00137 | | S | | D03338 | 7 | | | 150-199 |
| 663R | 22 | PB | BK | | 0-0 | 23-31-17 | SM00138 | | S | | D03338 | 6 | | | 150-199 |
| 664B | 22 | PB | BL | | 2-4 | 23-31-17 | SM00139 | | S | | D03340 | 7 | | | 150-199 |
| 664R | 22 | PB | BL | | 0-0 | 23-31-17 | SM00140 | | S | | D03340 | 6 | | | 150-199 |
| 666B | 22 | PB | DD | | 2-1 | 23-31-17 | SM00141 | | S | | D03344 | 7 | | | 150-199 |
| 666R | 22 | PB | DD | | 0-0 | 23-31-17 | SM00142 | | S | | D03344 | 6 | | | 150-199 |
| 667B | 22 | PB | DF | | 1-9 | 23-31-17 | SM00101 | | S | | D03346 | 7 | | | 150-199 |
| 667R | 22 | PB | DF | | 0-0 | 23-31-17 | SM00102 | | S | | D03346 | 6 | | | 150-199 |
| 668B | 22 | PB | DN | | 1-10 | 23-31-17 | SM00221 | | S | | D08166 | 7 | | | 150-199 |
| 668R | 22 | PB | DN | | 0-0 | 23-31-17 | SM00219 | | S | | D08166 | 6 | | | 150-199 |
| 669B | 22 | PB | DO | | 1-9 | 23-31-17 | SM00144 | | S | | D08168 | 7 | | | 150-199 |
| 669R | 22 | PB | DO | | 0-0 | 23-31-17 | SM00143 | | S | | D08168 | 6 | | | 150-199 |
| 670B | 22 | PB | DP | | 3-1 | 23-31-17 | SM00144 | | S | | D08170 | 7 | | | 150-199 |
| 670R | 22 | PB | DP | | 0-0 | 23-31-17 | SM00143 | | S | | D08170 | 6 | | | 150-199 |
| 671B | 22 | PB | DQ | | 2-8 | 23-31-17 | SM00114 | | S | | D08172 | 7 | | | 150-199 |
| 671R | 22 | PB | DQ | | 0-0 | 23-31-17 | SM00113 | | S | | D08172 | 6 | | | 150-199 |
| 700 | 20 | PA | | | 24-4 | 33-24-12 | SP03900 | | 9 | | SM00058 | | S | | 050-099 |
| 700 | 20 | PA | | | 28-2 | 33-24-12 | SP03900 | | 9 | | SM00134 | | S | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 18
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0810 | 286T0810 | | | SPEAKERS AND PASS. SIGNS,AFT RIGHT (continued) | | | | | | | | | | | | | |
| 701 | 20 | | PA | 24-4 | 33-24-12 | SP03898 | | | | | | | | | | | 050-099 |
| 701 | 20 | | PA | 28-2 | 33-24-12 | SP03898 | | | | | | | | | | | 150-199 |
| W0811 | 286T0811 | | | SATCOM SYSTEM,SIDE-MOUNTED HGA SUBSYSTEM-PORT | | | | | | | | | | | | | |
| 001 | 20 | | PA | 51-0 | 23-25-17 | D06171J | | | 14 | | D02693 | | M | | | | 156-157, 166-199, 277-299 |
| 002 | 20 | | PA | 49-0 | 23-25-17 | D06171J | | | 15 | | D02709 | | F | | | | 156-157, 166-199, 277-299 |
| 004 | 24 | | PK | 9-0 | 23-25-17 | D02693 | | | A- | | D02709 | | B | | | | 156-157, 166-199, 277-299 |
| 005 | 24 | | PK | 9-0 | 23-25-17 | D02693 | | | C- | | D02709 | | H | | | | 156-157, 166-199, 277-299 |
| 006 | 20 | | PA | 2-0 | 23-25-17 | D02693 | | | L | | GD06887 | | A.. | 2 | | | 156-157, 166-199 |
| 006 | 20 | | PA | 2-0 | 23-25-17 | D02693 | | | L | | STA1094 | | REF | = | | | 277-299 |
| 007 | 20 | | PA | 2-0 | 23-25-17 | D02693 | | | B- | | GD06887 | | D.. | 2 | | | 156-157, 166-199 |
| 007 | 20 | | PA | 2-0 | 23-25-17 | D02693 | | | B- | | STA1094 | | REF | = | | | 277-299 |
| 008 | 20 | | PA | 12-0 | 23-25-17 | D02709 | | | E | | GD01750 | | A.. | 2 | | | 156-157, 166-199, 277-299 |
| 009 | 20 | | PA | 12-0 | 23-25-17 | D02709 | | | A | | GD01750 | | S.. | 2 | | | 156-157, 166-199, 277-299 |
| 010 | 24 | | PK | 13-0 | 23-25-17 | D02677 | | | C | | D02693 | | V | | | | 156-157, 166-199, 277-278 |
| 010 | 24 | | PK | 12-0 | 23-25-17 | D02677 | | | C | | D02693 | | V | | | | 280-299 |
| 011 | 24 | | PK | 13-0 | 23-25-17 | D02677 | | | B | | D02693 | | Y | | | | 156-157, 166-199, 277-278 |
| 011 | 24 | | PK | 12-0 | 23-25-17 | D02677 | | | B | | D02693 | | Y | | | | 280-299 |
| 012 | 24 | | PK | 6-0 | 23-25-17 | D02677 | | | D | | SP00527 | | | 9 | | | 156-157, 166-199, 277-299 |
| 013 | 20 | | PA | 5-0 | 23-25-17 | D02677 | | | A | | GD01750 | | D.. | 2 | | | 156-157, 166-199, 277-299 |
| 014 | 24 | | PK | 1-0 | 23-25-17 | D02693 | | | A | | SM00001 | | | W | | | 156-157, 166-199, 277-299 |
| 016 | 24 | | PK | 1-0 | 23-25-17 | D02693 | | | D | | SM00001 | | | W | | | 156-157, 166-199, 277-299 |
| 017 | 24 | | PK | 1-0 | 23-25-17 | D02693 | | | C | | SM00001 | | | W | | | 156-157, 166-199, 277-299 |
| 018 | 24 | | PK | 9-0 | 23-25-17 | D02693 | | | CAP | Y | D02709 | | | J | | | 156-157, 166-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 19

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0811 | 286T0811 | | | SATCOM SYSTEM,SIDE-MOUNTED HGA SUBSYSTEM-PORT (continued) | | | | | | | | | | | |
| 201B | 24 | PL | IA | 51-0 | 23-25-17 | D06171J | | 2 | | D02693 | | F | | 156-157, 166-199, 277-299 | |
| 201R | 24 | PL | IA | 0-0 | 23-25-17 | D06171J | | 1 | | D02693 | | E | | 156-157, 166-199, 277-299 | |
| 202 | 20 | UA | | 1-6 | 23-25-17 | D02693 | | REF | IB | GD06887 | | D.. | 2 | 156-157, 166-199 | |
| 202 | 20 | UA | | 1-6 | 23-25-17 | D02693 | | REF | IB | STA1094 | | REF | = | 277-299 | |
| 202B | 24 | PW | IB | 51-0 | 23-25-17 | D06171J | | 4 | | D02693 | | X | | 156-157, 166-199, 277-299 | |
| 202R | 24 | PW | IB | 0-0 | 23-25-17 | D06171J | | 3 | | D02693 | | W | | 156-157, 166-199, 277-299 | |
| 202Z | | | IB | 0-0 | 23-25-17 | D06171J | | 5 | | D02693 | | REF | | IB 156-157, 166-199, 277-299 | |
| 203 | 20 | UA | | 1-6 | 23-25-17 | D02693 | | REF | IC | GD06887 | | D.. | 2 | 156-157, 166-199 | |
| 203 | 20 | UA | | 1-6 | 23-25-17 | D02693 | | REF | IC | STA1094 | | REF | = | 277-299 | |
| 203B | 24 | PW | IC | 51-0 | 23-25-17 | D06171J | | 7 | | D02693 | | R | | 156-157, 166-199, 277-299 | |
| 203R | 24 | PW | IC | 0-0 | 23-25-17 | D06171J | | 6 | | D02693 | | P | | 156-157, 166-199, 277-299 | |
| 203Z | | | IC | 0-0 | 23-25-17 | D06171J | | 8 | | D02693 | | REF | | IC 156-157, 166-199, 277-299 | |
| 204 | 20 | UA | | 1-6 | 23-25-17 | D02693 | | REF | ID | GD06887 | | D.. | 2 | 156-157, 166-199 | |
| 204 | 20 | UA | | 1-6 | 23-25-17 | D02693 | | REF | ID | STA1094 | | REF | = | 277-299 | |
| 204B | 24 | PW | ID | 51-0 | 23-25-17 | D06171J | | 10 | | D02693 | | U | | 156-157, 166-199, 277-299 | |
| 204R | 24 | PW | ID | 0-0 | 23-25-17 | D06171J | | 9 | | D02693 | | T | | 156-157, 166-199, 277-299 | |
| 204Z | | | ID | 0-0 | 23-25-17 | D06171J | | 11 | | D02693 | | REF | | ID 156-157, 166-199, 277-299 | |
| 205B | 20 | PB | IE | 13-0 | 23-25-17 | D02677 | | H | | D02693 | | K | | 156-157, 166-199, 277-299 | |
| 205R | 20 | PB | IE | 0-0 | 23-25-17 | D02677 | | F | | D02693 | | N | | 156-157, 166-199, 277-299 | |
| 206B | 24 | PL | IF | 51-0 | 23-25-17 | D06171J | | 13 | | D02693 | | H | | 156-157, 166-199, 277-299 | |
| 206R | 24 | PL | IF | 0-0 | 23-25-17 | D06171J | | 12 | | D02693 | | G | | 156-157, 166-199, 277-299 | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT | | | | | | | | | | | |
| 009 | 22 | PQ | AI | 58-0 | 33-51-11 | D05808P | | 9 | | D05112P | | 7 | | 050-099 | |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 20
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | |
| 009 | 22 | PQ | AI | 72-0 | 33-51-11 | D05110P | 6 | | | | | D05112P | 7 | | 150-199 | |
| 009 | 22 | PQ | AI | 69-0 | 33-51-11 | D05110P | 6 | | | | | D05112P | 7 | | 275-299 | |
| 009Z | | | AI | 0-0 | 33-51-11 | D05808P | DED | | | | | D05112P | DED | | 050-099 | |
| 009Z | | | AI | 0-0 | 33-51-11 | D05110P | DED | | | | | D05112P | DED | | 150-199, 275-299 | |
| 014 | 18 | PA | | 59-0 | 33-21-34 | D05110P | 9 | DL | | | | D05112P | 5 | | 050-099 | |
| 017 | 20 | PA | | 58-0 | 33-26-11 | D05110P | 3 | | | | | D05112P | 3 | | 050-099 | |
| 017 | 20 | PA | | 62-0 | 33-26-11 | D05110P | 3 | | | | | SP03634 | 9 | | 150-199 | |
| 017 | 20 | PA | | 69-0 | 33-26-11 | D05110P | 3 | | | | | D05112P | 3 | | 275-278 | |
| 017 | 20 | PA | | 70-0 | 33-26-11 | D05110P | 3 | | | | | D05112P | 3 | | 280-299 | |
| 01G | 20 | PA | | 20-0 | 33-21-32 | D05110P | 10 | | | | | SM00043 | 9 | | 050-099 | |
| 01J | 24 | PK | | 14-0 | 33-21-12 | D05110P | 1 | | | | | D08688J | 21 | | 050-099 | |
| 01K | 24 | PK | | 59-0 | 33-21-12 | D05110P | 56 | | | | | D06736P | 4 | | 050-099 | |
| 01L | 20 | PA | | 14-0 | 33-26-21 | D05110P | 19 | | | | | D08688J | 33 | | 050-099 | |
| 01M | 20 | PA | | 14-0 | 33-26-21 | D05110P | 57 | | | | | D08688J | 32 | | 050-099 | |
| 01N | 20 | PA | | 14-0 | 33-26-21 | D05110P | 15 | | | | | D08688J | 31 | | 050-099 | |
| 01P | 20 | PA | | 14-0 | 33-26-21 | D05110P | 16 | | | | | D08688J | 30 | | 050-099 | |
| 01S | 16 | PA | | 38-0 | 33-21-32 | D05110P | 27 | | | | | D12378 | 5 | FM | 280-299 | |
| 01T | 16 | PA | | 17-0 | 33-21-32 | D12378 | 8 | FM | | | | GD04844 | S.. | E | 280-299 | |
| 01W | 22 | PA | | 17-0 | 33-21-32 | D12380 | 3 | | | | | D12378 | 11 | | 280-299 | |
| 01X | 22 | PA | | 17-0 | 33-21-32 | D12380 | 4 | | | | | D12378 | 12 | | 280-299 | |
| 01Y | 22 | PA | | 17-0 | 33-21-32 | D12380 | 1 | | | | | D12378 | 9 | | 280-299 | |
| 020 | 20 | PA | | 7-0 | 33-21-32 | SM00043 | | 9 | | | | D02168 | 5 | | 050-099 | |
| 020 | 20 | PA | | 25-0 | 33-21-32 | D05110P | 4 | | | | | D02168 | 5 | | 150-154, 157-165, 167-199, 275-278 | |
| 020 | 20 | PQ | AT | 25-0 | 33-21-32 | D05110P | 4 | | | | | D02168 | 5 | | 155-156, 166 | |
| 020 | 20 | PA | | 27-0 | 33-21-32 | D05110P | 4 | | | | | D02168 | 5 | | 280-299 | |
| 020Z | | | AT | 0-0 | 33-21-32 | D05110P | DED | | | | | D02168 | DED | | 155-156, 166 | |
| 022 | 22 | PA | | 53-0 | 33-21-34 | D05110P | 8 | | | | | SM00003 | 9 | | 050-099 | |
| 023 | 20 | PA | | 39-0 | 33-21-32 | D05110P | 25 | | | | | D02940 | 5 | | 050-099 | |
| 023 | 20 | PA | | 50-0 | 33-21-32 | D05110P | 25 | | | | | D02940 | 5 | | 150-154, 157-165, 167-199, 275-278 | |
| 023 | 20 | PQ | AW | 55-0 | 33-21-32 | D05110P | 25 | | | | | D02940 | 5 | | 155-156, 166 | |
| 023 | 20 | PA | | 51-0 | 33-21-32 | D05110P | 25 | | | | | D02940 | 5 | | 280-299 | |
| 023Z | | | AW | 0-0 | 33-21-32 | D05110P | DED | | | | | D02940 | DED | | 155-156, 166 | |
| 024 | 20 | PA | | 3-0 | 33-21-32 | GD01014 | A.. | E | | | | D02940 | 7 | | 050-099 | |
| 024 | 20 | PA | | 11-0 | 33-21-32 | GD00685 | A.. | E | | | | D02940 | 7 | | 150-154, 157-165, 167-199 | |
| 024 | 20 | PQ | AX | 11-0 | 33-21-32 | GD00685 | A.. | E | | | | D02940 | 7 | | 155-156, 166 | |
| 024 | 20 | PA | | 5-0 | 33-21-32 | GD01014 | A.. | E | | | | D02940 | 7 | | 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 21

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|----------|------|------|--------|----------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | |
| 024Z | | | | AX | 0-0 | 33-21-32 | GD00685 | | DED | | D02940 | | DED | | 155-156, 166 |
| 025 | 20 | | PA | | 3-0 | 33-21-32 | GD01544 | | S.. | E | D02940 | | 8 | | 050-099 |
| 025 | 20 | | PA | | 11-0 | 33-21-32 | GD00681 | | S.. | E | D02940 | | 8 | | 150-199 |
| 025 | 20 | | PA | | 5-0 | 33-21-32 | GD01544 | | S.. | E | D02940 | | 8 | | 275-299 |
| 026 | 20 | | PA | | 4-0 | 33-21-32 | D02168 | | | | GD01546 | | S.. | E | ALL |
| 027 | 20 | | PA | | 3-0 | 33-21-32 | D02168 | | | | GD01010 | | A.. | E | 050-099 |
| 027 | 20 | | PA | | 4-0 | 33-21-32 | D02168 | | | | GD01010 | | A.. | E | 150-154, 157-165, 167-199, 275-299 |
| 027 | 20 | | PQ | BB | 4-0 | 33-21-32 | D02168 | | | 7 | GD01010 | | A.. | E | 155-156, 166 |
| 027Z | | | | BB | 0-0 | 33-21-32 | D02168 | | DED | | GD01010 | | DED | | 155-156, 166 |
| 028 | 22 | | PA | | 20-0 | 33-21-32 | D02168 | | | 2 | D03190 | | 1 | | 050-099 |
| 028 | 22 | | PA | | 19-0 | 33-21-32 | D02168 | | | 2 | D03190 | | 1 | | 150-199, 275-299 |
| 029 | 22 | | PA | | 20-0 | 33-21-32 | D02168 | | | 3 | D03190 | | 2 | | 050-099, 150-199, 275-278 |
| 029 | 22 | | PA | | 19-0 | 33-21-32 | D02168 | | | 3 | D03190 | | 2 | | 280-299 |
| 02D | 20 | | PA | | 40-0 | 33-21-13 | STA0654R | | CAP | Y | SM00055 | | | 9 | 280-299 |
| 02E | 20 | | PA | | 41-0 | 33-21-13 | SM00055 | | | 9 | STA0719R | | CAP | Y | 280-299 |
| 02F | 20 | | PA | | 14-0 | 33-21-13 | STA0654L | | CAP | Y | SM00056 | | | 9 | 280-299 |
| 02G | 20 | | PA | | 3-0 | 33-21-13 | SM00056 | | | 9 | STA0719L | | CAP | Y | 280-299 |
| 02N | 20 | | PA | | 30-0 | 33-21-11 | SM00075 | | | 9 | ST0675R | | CAP | Y | 280-299 |
| 02P | 20 | | PA | | 30-0 | 33-21-11 | SM00074 | | | 9 | ST0675R | | CAP | Y | 280-299 |
| 02R | 16 | | PA | | 9-0 | 33-21-32 | D12378 | | | 7 | GD04842 | | A.. | E | 280-299 |
| 02S | 20 | | PA | | 14-0 | 33-21-32 | D12380 | | | 5 | GD04870 | | S.. | E | 280-299 |
| 02T | 22 | | PA | | 17-0 | 33-21-32 | D12380 | | | 2 | D12378 | | 10 | | 280-299 |
| 02U | 20 | | PA | | 29-0 | 33-21-11 | SP05246 | | | 9 | STA0707L | | CAP | Y | 280-299 |
| 02V | 20 | | PA | | 29-0 | 33-21-11 | SP05244 | | | 9 | STA0707L | | CAP | Y | 280-299 |
| 02W | 20 | | PA | | 24-0 | 33-21-11 | D12372 | | | 11 | SP05244 | | | 9 | 280-299 |
| 02X | 20 | | PA | | 24-0 | 33-21-11 | D12372 | | | 12 | SP05246 | | | 9 | 280-299 |
| 02Y | 20 | | PA | | 4-0 | 33-21-11 | D12372 | | | 7 | GD04818 | | A.. | E | 280-299 |
| 02Z | 20 | | PA | | 5-0 | 33-21-11 | D12372 | | | 8 | GD04820 | | S.. | E | 280-299 |
| 030 | 22 | | PA | | 7-0 | 33-21-32 | D02168 | | | 11 | SM00037 | | | 9 | 050-099, 150-199, 275-278 |
| 030 | 22 | | PA | | 5-0 | 33-21-32 | D02168 | | | 11 | SM00037 | | | 9 | 280-299 |
| 031 | 22 | | PA | | 7-0 | 33-21-32 | D02168 | | | 12 | SM00038 | | | 9 | 050-099, 150-199, 275-278 |
| 031 | 22 | | PA | | 5-0 | 33-21-32 | D02168 | | | 12 | SM00038 | | | 9 | 280-299 |
| 033 | 22 | | PA | | 12-0 | 33-21-32 | D02940 | | | 2 | D03084 | | 1 | | 050-099 |
| 033 | 22 | | PA | | 19-0 | 33-21-32 | D02940 | | | 2 | D03084 | | 1 | | 150-199 |
| 033 | 22 | | PA | | 14-0 | 33-21-32 | D02940 | | | 2 | D03084 | | 1 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 22

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|--------|-------|------|----------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| 034 | 22 | | PA | 12-0 | 33-21-32 | D02940 | | | 3 | | | | D03084 | 2 | | | 050-099 |
| 034 | 22 | | PA | 19-0 | 33-21-32 | D02940 | | | 3 | | | | D03084 | 2 | | | 150-199 |
| 034 | 22 | | PA | 14-0 | 33-21-32 | D02940 | | | 3 | | | | D03084 | 2 | | | 275-299 |
| 035 | 22 | | PA | 12-0 | 33-21-32 | SM00004 | | | | 9 | | | D03084 | 3 | | | 050-099 |
| 035 | 22 | | PA | 28-0 | 33-21-32 | SM00004 | | | | 9 | | | D03084 | 3 | | | 150-199, 275-278 |
| 035 | 22 | | PA | 26-0 | 33-21-32 | SM00004 | | | | 9 | | | D03084 | 3 | | | 280-299 |
| 036 | 22 | | PA | 12-0 | 33-21-32 | SM00005 | | | | 9 | | | D03084 | 4 | | | 050-099 |
| 036 | 22 | | PA | 28-0 | 33-21-32 | SM00005 | | | | 9 | | | D03084 | 4 | | | 150-199, 275-278 |
| 036 | 22 | | PA | 26-0 | 33-21-32 | SM00005 | | | | 9 | | | D03084 | 4 | | | 280-299 |
| 037 | 22 | | PA | 22-0 | 33-21-32 | SM00004 | | | | 9 | | | D03116 | 3 | | | 050-099, 280-299 |
| 037 | 22 | | PA | 2-0 | 33-21-32 | SM00004 | | | | 9 | | | D03116 | 3 | | | 150-199, 275-278 |
| 038 | 22 | | PA | 22-0 | 33-21-32 | SM00005 | | | | 9 | | | D03116 | 4 | | | 050-099, 280-299 |
| 038 | 22 | | PA | 2-0 | 33-21-32 | SM00005 | | | | 9 | | | D03116 | 4 | | | 150-199, 275-278 |
| 039 | 22 | | PA | 22-0 | 33-21-32 | D02940 | | | | 9 | | | D03116 | 1 | | | 050-099, 275-299 |
| 039 | 22 | | PA | 26-0 | 33-21-32 | D02940 | | | | 9 | | | D03116 | 1 | | | 150-199 |
| 03B | 20 | | PA | 16-0 | 33-21-11 | D12372 | | | | 2 | | | STA0707L | CAP | Y | | 280-299 |
| 03C | 20 | | PA | 16-0 | 33-21-11 | D12372 | | | | 3 | | | STA0707L | CAP | Y | | 280-299 |
| 03D | 20 | | PA | 41-0 | 33-21-11 | D12372 | | | | 9 | | | STA0707R | CAP | Y | | 280-299 |
| 03F | 20 | | PA | 41-0 | 33-21-11 | D12372 | | | | 10 | | | STA0707R | CAP | Y | | 280-299 |
| 03G | 20 | | PA | 6-0 | 33-21-11 | D12372 | | | | 5 | | | SM00041 | | 9 | | 280-299 |
| 03H | 20 | | PA | 22-0 | 33-21-13 | SM00063 | | | | 9 | | | STA0719R | CAP | Y | | 280-299 |
| 03I | 20 | | PA | 22-0 | 33-21-13 | SM00064 | | | | 9 | | | STA0719R | CAP | Y | | 280-299 |
| 03J | 20 | | PA | 25-0 | 33-21-13 | STA0654R | | | | | CAP | Y | SM00063 | | 9 | | 280-299 |
| 03K | 20 | | PA | 25-0 | 33-21-13 | STA0654R | | | | | CAP | Y | SM00064 | | 9 | | 280-299 |
| 03L | 20 | | PA | 17-0 | 33-21-13 | SM00065 | | | | 9 | | | STA0719R | CAP | Y | | 280-299 |
| 03M | 20 | | PA | 18-0 | 33-21-13 | SM00065 | | | | 9 | | | STA0654R | CAP | Y | | 280-299 |
| 03N | 20 | | PA | 18-0 | 33-21-13 | SM00066 | | | | 9 | | | STA0654R | CAP | Y | | 280-299 |
| 03P | 20 | | PA | 17-0 | 33-21-13 | SM00066 | | | | 9 | | | STA0719R | CAP | Y | | 280-299 |
| 03R | 20 | | PA | 8-0 | 33-21-13 | SM00068 | | | | 9 | | | STA0719L | CAP | Y | | 280-299 |
| 03S | 20 | | PA | 8-0 | 33-21-13 | SM00067 | | | | 9 | | | STA0719L | CAP | Y | | 280-299 |
| 03T | 20 | | PA | 7-0 | 33-21-13 | SM00069 | | | | 9 | | | STA0719L | CAP | Y | | 280-299 |
| 03U | 20 | | PA | 7-0 | 33-21-13 | SP00818 | | | | 9 | | | SM00068 | | 9 | | 280-299 |
| 03V | 20 | | PA | 8-0 | 33-21-13 | SP00816 | | | | 9 | | | SM00067 | | 9 | | 280-299 |
| 03W | 20 | | PA | 11-0 | 33-21-13 | STA0654L | | | | | CAP | Y | SM00069 | | 9 | | 280-299 |
| 03X | 20 | | PA | 11-0 | 33-21-13 | STA0654L | | | | | CAP | Y | SM00070 | | 9 | | 280-299 |
| 03Y | 20 | | PA | 7-0 | 33-21-13 | SM00070 | | | | 9 | | | STA0719L | CAP | Y | | 280-299 |
| 040 | 22 | | PA | 22-0 | 33-21-32 | D02940 | | | | 10 | | | D03116 | 2 | | | 050-099, 275-299 |
| 040 | 22 | | PA | 26-0 | 33-21-32 | D02940 | | | | 10 | | | D03116 | 2 | | | 150-199 |
| 041 | 22 | | PA | 7-0 | 33-21-32 | D02940 | | | | 11 | | | SM00004 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 23

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | |
| 041 | 22 | | PA | | 26-0 | 33-21-32 | D02940 | | 11 | | SM00004 | | 9 | | 150-199 |
| 041 | 22 | | PA | | 22-0 | 33-21-32 | D02940 | | 11 | | SM00004 | | 9 | | 275-278 |
| 041 | 22 | | PA | | 21-0 | 33-21-32 | D02940 | | 11 | | SM00004 | | 9 | | 280-299 |
| 042 | 22 | | PA | | 7-0 | 33-21-32 | D02940 | | 12 | | SM00005 | | 9 | | 050-099 |
| 042 | 22 | | PA | | 26-0 | 33-21-32 | D02940 | | 12 | | SM00005 | | 9 | | 150-199 |
| 042 | 22 | | PA | | 22-0 | 33-21-32 | D02940 | | 12 | | SM00005 | | 9 | | 275-278 |
| 042 | 22 | | PA | | 21-0 | 33-21-32 | D02940 | | 12 | | SM00005 | | 9 | | 280-299 |
| 043 | 22 | | PA | | 14-0 | 33-21-34 | SM00003 | | | 9 | D02942 | | 5 | | 050-099 |
| 043 | 16 | | PA | | 65-0 | 33-21-34 | D05808P | | 4 | | D02942 | | 5 | FM | 150-154, 157-165, 167-199 |
| 043 | 16 | | PQ | BR | 65-0 | 33-21-34 | D05808P | | 4 | | D02942 | | 5 | FM | 155-156, 166 |
| 043 | 16 | | PA | | 64-0 | 33-21-34 | D05808P | | 4 | | D02942 | | 5 | FM | 275-299 |
| 043Z | | | | BR | 0-0 | 33-21-34 | D05808P | | DED | | D02942 | | DED | | 155-156, 166 |
| 044 | 20 | | PA | | 8-0 | 33-21-34 | GD01550 | | A.. | E | D02942 | | 7 | | 050-099 |
| 044 | 16 | | PA | | 9-0 | 33-21-34 | GD04628 | | A.. | E | D02942 | | 7 | FM | 150-154, 157-165, 167-199 |
| 044 | 16 | | PQ | BS | 9-0 | 33-21-34 | GD04628 | | A.. | E | D02942 | | 7 | FM | 155-156, 166 |
| 044 | 16 | | PA | | 4-0 | 33-21-34 | GD04866 | | A.. | E | D02942 | | 7 | FM | 275-299 |
| 044Z | | | | BS | 0-0 | 33-21-34 | GD04628 | | DED | | D02942 | | DED | | 155-156, 166 |
| 045 | 20 | | PA | | 4-0 | 33-21-34 | GD02902 | | S.. | E | D02942 | | 8 | | 050-099 |
| 045 | 16 | | PA | | 9-0 | 33-21-34 | GD04630 | | S.. | E | D02942 | | 8 | FM | 150-199 |
| 045 | 16 | | PA | | 4-0 | 33-21-34 | GD04834 | | S.. | E | D02942 | | 8 | FM | 275-299 |
| 046 | 22 | | PA | | 7-0 | 33-21-34 | SM00003 | | | 9 | D02944 | | 5 | | 050-099 |
| 046 | 20 | | PA | | 63-0 | 33-21-34 | D05110P | | 8 | | D02944 | | 5 | | 275-278 |
| 046 | 20 | | PA | | 67-0 | 33-21-34 | D05110P | | 8 | | D02944 | | 5 | | 280-299 |
| 047 | 20 | | PA | | 4-0 | 33-21-34 | GD01554 | | A.. | E | D02944 | | 7 | | 050-099 |
| 047 | 20 | | PA | | 4-0 | 33-21-34 | GD04866 | | A.. | E | D02944 | | 7 | | 275-278 |
| 047 | 20 | | PA | | 5-0 | 33-21-34 | GD04866 | | A.. | E | D02944 | | 7 | | 280-299 |
| 048 | 20 | | PA | | 4-0 | 33-21-34 | GD01556 | | S.. | E | D02944 | | 8 | | 050-099 |
| 048 | 20 | | PA | | 4-0 | 33-21-34 | GD04834 | | S.. | E | D02944 | | 8 | | 275-278 |
| 048 | 20 | | PA | | 5-0 | 33-21-34 | GD04834 | | S.. | E | D02944 | | 8 | | 280-299 |
| 049 | 22 | | PA | | 14-0 | 33-21-34 | D02942 | | 2 | | D03088 | | 1 | | 050-099 |
| 049 | 22 | | PA | | 11-0 | 33-21-34 | D02942 | | 2 | | D03088 | | 1 | | 150-199 |
| 049 | 22 | | PA | | 16-0 | 33-21-34 | D02942 | | 2 | | D03088 | | 1 | | 275-299 |
| 04B | 20 | | PA | | 9-0 | 33-21-13 | D20032 | | 2 | | SM00066 | | 9 | | 280-299 |
| 04C | 20 | | PA | | 9-0 | 33-21-13 | D20032 | | 3 | | SM00065 | | 9 | | 280-299 |
| 04D | 20 | | PA | | 9-0 | 33-21-13 | D20032 | | 12 | | SM00068 | | 9 | | 280-299 |
| 04E | 20 | | PA | | 9-0 | 33-21-13 | D20032 | | 11 | | SM00067 | | 9 | | 280-299 |
| 04F | 20 | | PA | | 11-0 | 33-21-13 | D20032 | | 9 | | SM00069 | | 9 | | 280-299 |

WIRE LIST

D280T132

91-21-11
Section W0810
Page 24
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | | |
| 04G | 20 | | PA | 11-0 | 33-21-13 | D20032 | | 10 | | | | | SM00070 | | | | 9 | 280-299 |
| 04H | 20 | | PA | 4-0 | 33-21-13 | D20032 | | 7 | | | | | GD04818 | A.. | E | | | 280-299 |
| 04I | 20 | | PA | 15-0 | 33-21-13 | D20032 | | 5 | | | | | SM00073 | | | | 9 | 280-299 |
| 04J | 20 | | PA | 4-0 | 33-21-13 | D20032 | | 8 | | | | | GD04820 | S.. | E | | | 280-299 |
| 04K | 20 | | PA | 38-0 | 33-21-13 | D05112P | | 20 | | | | | SM00073 | | | | 9 | 280-299 |
| 050 | 22 | | PA | 14-0 | 33-21-34 | D02942 | | 3 | | | | | D03088 | | 2 | | | 050-099 |
| 050 | 22 | | PA | 11-0 | 33-21-34 | D02942 | | 3 | | | | | D03088 | | 2 | | | 150-199 |
| 050 | 22 | | PA | 16-0 | 33-21-34 | D02942 | | 3 | | | | | D03088 | | 2 | | | 275-299 |
| 051 | 22 | | PA | 17-0 | 33-21-34 | SM00006 | | | 9 | | | | D03088 | | 3 | | | 050-099 |
| 051 | 22 | | PA | 14-0 | 33-21-34 | SM00006 | | | 9 | | | | D03088 | | 3 | | | 150-199, 275-299 |
| 052 | 22 | | PA | 12-0 | 33-21-34 | SM00007 | | | 9 | | | | D03088 | | 4 | | | 050-099 |
| 052 | 22 | | PA | 14-0 | 33-21-34 | SM00007 | | | 9 | | | | D03088 | | 4 | | | 150-199, 275-299 |
| 053 | 22 | | PA | 16-0 | 33-21-34 | SM00006 | | | 9 | | | | D03090 | | 3 | | | 050-099 |
| 053 | 22 | | PA | 14-0 | 33-21-34 | SM00008 | | | 9 | | | | D03090 | | 3 | | | 275-278 |
| 053 | 22 | | PA | 12-0 | 33-21-34 | SM00008 | | | 9 | | | | D03090 | | 3 | | | 280-299 |
| 054 | 22 | | PA | 16-0 | 33-21-34 | SM00007 | | | 9 | | | | D03090 | | 4 | | | 050-099 |
| 054 | 22 | | PA | 14-0 | 33-21-34 | SM00009 | | | 9 | | | | D03090 | | 4 | | | 275-278 |
| 054 | 22 | | PA | 12-0 | 33-21-34 | SM00009 | | | 9 | | | | D03090 | | 4 | | | 280-299 |
| 055 | 22 | | PA | 11-0 | 33-21-34 | D02942 | | | 9 | | | | D03090 | | 1 | | | 050-099 |
| 055 | 22 | | PA | 13-0 | 33-21-34 | D02944 | | | 9 | | | | D03090 | | 1 | | | 275-278 |
| 055 | 22 | | PA | 14-0 | 33-21-34 | D02944 | | | 9 | | | | D03090 | | 1 | | | 280-299 |
| 056 | 22 | | PA | 11-0 | 33-21-34 | D02942 | | | 10 | | | | D03090 | | 2 | | | 050-099 |
| 056 | 22 | | PA | 13-0 | 33-21-34 | D02944 | | | 10 | | | | D03090 | | 2 | | | 275-278 |
| 056 | 22 | | PA | 14-0 | 33-21-34 | D02944 | | | 10 | | | | D03090 | | 2 | | | 280-299 |
| 057 | 22 | | PA | 14-0 | 33-21-34 | D02942 | | | 11 | | | | SM00006 | | | | 9 | 050-099 |
| 057 | 22 | | PA | 9-0 | 33-21-34 | D02942 | | | 11 | | | | SM00006 | | | | 9 | 150-199 |
| 057 | 22 | | PA | 7-0 | 33-21-34 | D02942 | | | 11 | | | | SM00006 | | | | 9 | 275-299 |
| 058 | 22 | | PA | 14-0 | 33-21-34 | D02942 | | | 12 | | | | SM00007 | | | | 9 | 050-099 |
| 058 | 22 | | PA | 9-0 | 33-21-34 | D02942 | | | 12 | | | | SM00007 | | | | 9 | 150-199 |
| 058 | 22 | | PA | 7-0 | 33-21-34 | D02942 | | | 12 | | | | SM00007 | | | | 9 | 275-299 |
| 059 | 22 | | PA | 14-0 | 33-21-34 | D02944 | | | 2 | | | | D03092 | | | 1 | | 050-099 |
| 059 | 22 | | PA | 12-0 | 33-21-34 | D02944 | | | 2 | | | | D03092 | | | 1 | | 275-278 |
| 059 | 22 | | PA | 13-0 | 33-21-34 | D02944 | | | 2 | | | | D03092 | | | 1 | | 280-299 |
| 060 | 22 | | PA | 14-0 | 33-21-34 | D02944 | | | 3 | | | | D03092 | | | 2 | | 050-099 |
| 060 | 22 | | PA | 12-0 | 33-21-34 | D02944 | | | 3 | | | | D03092 | | | 2 | | 275-278 |
| 060 | 22 | | PA | 13-0 | 33-21-34 | D02944 | | | 3 | | | | D03092 | | | 2 | | 280-299 |
| 061 | 22 | | PA | 10-0 | 33-21-34 | SM00008 | | | 9 | | | | D03092 | | | 3 | | 050-099 |
| 061 | 22 | | PA | 8-0 | 33-21-34 | SM00008 | | | 9 | | | | D03092 | | | 3 | | 275-299 |
| 062 | 22 | | PA | 10-0 | 33-21-34 | SM00009 | | | 9 | | | | D03092 | | | 4 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 25

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | |
| 062 | 22 | PA | | | 8-0 | 33-21-34 | SM00009 | | 9 | | | D03092 | 4 | | 275-299 |
| 063 | 22 | PA | | | 20-0 | 33-21-34 | SM00008 | | 9 | | | D03124 | 3 | | 050-099 |
| 064 | 22 | PA | | | 20-0 | 33-21-34 | SM00009 | | 9 | | | D03124 | 4 | | 050-099 |
| 065 | 22 | PA | | | 22-0 | 33-21-34 | D02944 | | 9 | | | D03124 | 1 | | 050-099 |
| 066 | 22 | PA | | | 22-0 | 33-21-34 | D02944 | | 10 | | | D03124 | 2 | | 050-099 |
| 067 | 22 | PA | | | 6-0 | 33-21-34 | D02944 | | 11 | | | SM00008 | 9 | | 050-099 |
| 067 | 22 | PA | | | 7-0 | 33-21-34 | D02944 | | 11 | | | SM00008 | 9 | | 275-299 |
| 068 | 22 | PA | | | 7-0 | 33-21-34 | D02944 | | 12 | | | SM00009 | 9 | | 050-099, 275-299 |
| 069 | 22 | PA | | | 58-0 | 33-21-34 | D05110P | | 5 | | | D05112P | 4 | | 050-099 |
| 069 | 20 | PA | | | 72-0 | 33-21-34 | D05110P | | 15 | | | D05112P | 4 | | 150-154, 157-165, 167-199 |
| 069 | 20 | PQ | CS | | 72-0 | 33-21-34 | D05110P | | 15 | | | D05112P | 4 | | 155-156, 166 |
| 069 | 20 | PA | | | 69-0 | 33-21-34 | D05110P | | 15 | | | D05112P | 4 | | 275-278 |
| 069 | 20 | PA | | | 70-0 | 33-21-34 | D05110P | | 15 | | | D05112P | 4 | | 280-299 |
| 069Z | | | CS | | 0-0 | 33-21-34 | D05110P | DED | | | | D05112P | DED | | 155-156, 166 |
| 070 | 18 | PA | | | 50-0 | 33-21-34 | D05110P | | 6 | DL | | D02002 | 5 | DK | 050-099 |
| 070 | 16 | PA | | | 60-0 | 33-21-34 | D05808P | | 5 | | | D02002 | 5 | FM | 150-154, 157-165, 167-199 |
| 070 | 16 | PQ | CT | | 60-0 | 33-21-34 | D05808P | | 5 | | | D02002 | 5 | FM | 155-156, 166 |
| 070 | 16 | PA | | | 63-0 | 33-21-34 | D05808P | | 5 | | | SM00010 | 9 | | 275-278 |
| 070 | 16 | PA | | | 63-0 | 33-21-34 | D05808P | | 5 | FM | | SM00010 | 9 | | 280-299 |
| 070Z | | | CT | | 0-0 | 33-21-34 | D05808P | DED | | | | D02002 | DED | | 155-156, 166 |
| 071 | 16 | PA | | | 7-0 | 33-21-34 | SM00010 | | 9 | | | D05112P | 23 | | 275-278 |
| 071 | 16 | PA | | | 8-0 | 33-21-34 | SM00010 | | 9 | | | D05112P | 23 | FM | 280-299 |
| 072 | 16 | PA | | | 17-0 | 33-21-34 | SM00010 | | 9 | | | D02002 | 5 | FM | 275-278 |
| 072 | 16 | PA | | | 13-0 | 33-21-34 | SM00010 | | 9 | | | D02002 | 5 | FM | 280-299 |
| 073 | 18 | PA | | | 4-0 | 33-21-34 | GD01018 | | A.. | E | | D02002 | 7 | DK | 050-099 |
| 073 | 16 | PA | | | 12-0 | 33-21-34 | GD00685 | | A.. | E | | D02002 | 7 | FM | 150-154, 157-165, 167-199, 275-278 |
| 073 | 16 | PQ | CW | | 12-0 | 33-21-34 | GD00685 | | A.. | E | | D02002 | 7 | FM | 155-156, 166 |
| 073 | 16 | PA | | | 13-0 | 33-21-34 | GD00685 | | A.. | E | | D02002 | 7 | FM | 280-299 |
| 073Z | | | CW | | 0-0 | 33-21-34 | GD00685 | DED | | | | D02002 | DED | | 155-156, 166 |
| 074 | 18 | PA | | | 4-0 | 33-21-34 | GD01560 | | S.. | E | | D02002 | 8 | DK | 050-099 |
| 074 | 16 | PA | | | 12-0 | 33-21-34 | GD00681 | | S.. | E | | D02002 | 8 | FM | 150-199, 275-278 |
| 074 | 16 | PA | | | 13-0 | 33-21-34 | GD00681 | | S.. | E | | D02002 | 8 | FM | 280-299 |
| 075 | 22 | PA | | | 15-0 | 33-21-34 | D03096 | | 1 | | | D02002 | 2 | | 050-099 |
| 075 | 22 | PA | | | 14-0 | 33-21-34 | D03096 | | 1 | | | D02002 | 2 | | 150-199, 275-299 |
| 076 | 22 | PA | | | 15-0 | 33-21-34 | D03096 | | 2 | | | D02002 | 3 | | 050-099 |
| 076 | 22 | PA | | | 14-0 | 33-21-34 | D03096 | | 2 | | | D02002 | 3 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 26

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| 077 | 22 | | PA | 12-0 | 33-21-34 | D03096 | | 3 | | | | | SM00039 | | 9 | | 050-099 |
| 077 | 22 | | PA | 8-0 | 33-21-34 | D03096 | | 3 | | | | | SM00039 | | 9 | | 150-199, 275-278 |
| 077 | 22 | | PA | 9-0 | 33-21-34 | D03096 | | 3 | | | | | SM00039 | | 9 | | 280-299 |
| 078 | 22 | | PA | 12-0 | 33-21-34 | D03096 | | 4 | | | | | SM00040 | | 9 | | 050-099 |
| 078 | 22 | | PA | 8-0 | 33-21-34 | D03096 | | 4 | | | | | SM00040 | | 9 | | 150-199, 275-278 |
| 078 | 22 | | PA | 9-0 | 33-21-34 | D03096 | | 4 | | | | | SM00040 | | 9 | | 280-299 |
| 079 | 22 | | PA | 10-0 | 33-21-32 | D05110P | | 7 | | | | | D02946 | | 5 | | 050-099 |
| 079 | 20 | | PA | 10-0 | 33-21-32 | D05110P | | 7 | | | | | D02946 | | 5 | | 150-154, 157-165, 167-199, 275-278 |
| 079 | 20 | | PQ | B | 10-0 | 33-21-32 | D05110P | | 7 | | | | D02946 | | 5 | | 155-156, 166 |
| 079 | 20 | | PA | | 11-0 | 33-21-32 | D05110P | | 7 | | | | D02946 | | 5 | | 280-299 |
| 079Z | | | | B | 0-0 | 33-21-32 | D05110P | | DED | | | | D02946 | | DED | | 155-156, 166 |
| 080 | 20 | | PA | | 9-0 | 33-21-32 | GD01582 | | S.. | E | | | D02946 | | 8 | | 050-099 |
| 080 | 20 | | PA | | 4-0 | 33-21-32 | GD01582 | | S.. | E | | | D02946 | | 8 | | 150-199, 275-299 |
| 081 | 20 | | PA | | 9-0 | 33-21-32 | GD01022 | | A.. | E | | | D02946 | | 7 | | 050-099 |
| 081 | 20 | | PA | | 4-0 | 33-21-32 | GD01022 | | A.. | E | | | D02946 | | 7 | | 150-154, 157, 275-299 |
| 081 | 20 | | PQ | DF | 4-0 | 33-21-32 | GD01022 | | A.. | E | | | D02946 | | 7 | | 155-156 |
| 081 | 20 | | PA | | 4-0 | 33-21-32 | GD01022 | | A.. | E | * | | D02946 | | 7 | | 162-165, 167-199 |
| 081 | 20 | | PQ | DF | 4-0 | 33-21-32 | GD01022 | | A.. | E | * | | D02946 | | 7 | | 166 |
| 081Z | | | | DF | 0-0 | 33-21-32 | GD01022 | | DED | | | | D02946 | | DED | | 155-156, 166 |
| 083 | 20 | | PA | | 15-0 | 33-21-32 | SM00043 | | | 9 | | | D02170 | | 5 | | 050-099 |
| 083 | 20 | | PA | | 39-0 | 33-21-32 | D05110P | | | 9 | | | D02170 | | 5 | | 150-154, 275-278 |
| 083 | 20 | | PQ | DH | 48-0 | 33-21-32 | D05110P | | | 9 | | | D02170 | | 5 | | 155-156, 166 |
| 083 | 20 | | PA | | 48-0 | 33-21-32 | D05110P | | | 9 | | | D02170 | | 5 | | 157, 167-199 |
| 083 | 20 | | PA | | 43-0 | 33-21-32 | D05110P | | | 9 | | | D02170 | | 5 | | 162-165 |
| 083 | 20 | | PA | | 40-0 | 33-21-32 | D05110P | | | 9 | | | D02170 | | 5 | | 280-299 |
| 083Z | | | | DH | 0-0 | 33-21-32 | D05110P | | | DED | | | D02170 | | DED | | 155-156, 166 |
| 084 | 20 | | PA | | 10-0 | 33-21-32 | SM00043 | | | 9 | | | D02164 | | 5 | | 050-099 |
| 084 | 20 | | PA | | 18-0 | 33-21-32 | D05110P | | | 10 | | | D02164 | | 5 | | 150-154, 157, 275-299 |
| 084 | 20 | | PQ | DI | 18-0 | 33-21-32 | D05110P | | | 10 | | | D02164 | | 5 | | 155-156 |
| 084 | 20 | | PA | | 18-0 | 33-21-32 | D05110P | | | 10 | | | SM00053 | | 9 | | 162-163 |
| 084 | 20 | | PA | | 2-0 | 33-21-32 | D05110P | | | 10 | | | SM00053 | | 9 | | 164-165, 167-199 |
| 084 | 20 | | PQ | DI | 2-0 | 33-21-32 | D05110P | | | 10 | | | SM00053 | | 9 | | 166 |
| 084Z | | | | DI | 0-0 | 33-21-32 | D05110P | | | DED | | | D02164 | | DED | | 155-156 |
| 084Z | | | | DI | 0-0 | 33-21-32 | D05110P | | | DED | | | SM00053 | | DED | | 166 |
| 085 | 20 | | PA | | 4-0 | 33-21-32 | GD01586 | | S.. | E | | | D02164 | | 8 | | ALL |
| 086 | 20 | | PA | | 4-0 | 33-21-32 | GD01588 | | A.. | E | | | D02164 | | 7 | | 050-099, 150-154, 157-165, 167-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 27

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | |
| 086 | 20 | PQ | | DK | 4-0 | 33-21-32 | GD01588 | A.. | E | | D02164 | 7 | | | 155-156, 166 |
| 086Z | | | | DK | 0-0 | 33-21-32 | GD01588 | | | | D02164 | | DED | | 155-156, 166 |
| 091 | 22 | PA | | | 9-0 | 33-21-32 | SM00011 | | 9 | | D03100 | 3 | | | 275-278 |
| 091 | 22 | PA | | | 10-0 | 33-21-32 | SM00011 | | 9 | | D03100 | 3 | | | 280-299 |
| 092 | 22 | PA | | | 9-0 | 33-21-32 | SM00012 | | 9 | | D03100 | 4 | | | 275-278 |
| 092 | 22 | PA | | | 10-0 | 33-21-32 | SM00012 | | 9 | | D03100 | 4 | | | 280-299 |
| 093 | 22 | PA | | | 12-0 | 33-21-32 | D02946 | | 9 | | D03100 | 1 | | | 050-099 |
| 093 | 22 | PA | | | 13-0 | 33-21-32 | D02946 | | 9 | | D03100 | 1 | | | 150-199, 275-299 |
| 094 | 22 | PA | | | 12-0 | 33-21-32 | D02946 | | 10 | | D03100 | 2 | | | 050-099 |
| 094 | 22 | PA | | | 13-0 | 33-21-32 | D02946 | | 10 | | D03100 | 2 | | | 150-199, 275-299 |
| 095 | 22 | PA | | | 12-0 | 33-21-32 | D02946 | | 11 | | D03100 | 3 | | | 050-099 |
| 095 | 22 | PA | | | 20-0 | 33-21-32 | D02946 | | 11 | | D03100 | 3 | | | 150-199 |
| 095 | 22 | PA | | | 6-0 | 33-21-32 | D02946 | | 11 | | SM00011 | | 9 | | 275-299 |
| 096 | 22 | PA | | | 12-0 | 33-21-32 | D02946 | | 12 | | D03100 | 4 | | | 050-099 |
| 096 | 22 | PA | | | 20-0 | 33-21-32 | D02946 | | 12 | | D03100 | 4 | | | 150-199 |
| 096 | 22 | PA | | | 6-0 | 33-21-32 | D02946 | | 12 | | SM00012 | | 9 | | 275-299 |
| 097 | 22 | PA | | | 19-0 | 33-21-32 | D02164 | | 2 | | D03186 | 1 | | | 050-099 |
| 097 | 22 | PA | | | 20-0 | 33-21-32 | D02164 | | 2 | | D03186 | 1 | | | 150-199, 275-299 |
| 098 | 22 | PA | | | 19-0 | 33-21-32 | D02164 | | 3 | | D03186 | 2 | | | 050-099 |
| 098 | 22 | PA | | | 20-0 | 33-21-32 | D02164 | | 3 | | D03186 | 2 | | | 150-199, 275-299 |
| 099 | 22 | PA | | | 17-0 | 33-21-32 | SM00013 | | 9 | | D03186 | 3 | | | 050-099, 280-299 |
| 099 | 22 | PA | | | 18-0 | 33-21-32 | SM00013 | | 9 | | D03186 | 3 | | | 150-199, 275-278 |
| 100 | 22 | PA | | | 17-0 | 33-21-32 | SM00014 | | 9 | | D03186 | 4 | | | 050-099, 280-299 |
| 100 | 22 | PA | | | 18-0 | 33-21-32 | SM00014 | | 9 | | D03186 | 4 | | | 150-199, 275-278 |
| 101 | 22 | PA | | | 9-0 | 33-21-32 | SM00013 | | 9 | | D03104 | 3 | | | 050-099 |
| 101 | 22 | PA | | | 10-0 | 33-21-32 | SM00013 | | 9 | | D03104 | 3 | | | 150-199, 275-299 |
| 102 | 22 | PA | | | 9-0 | 33-21-32 | SM00014 | | 9 | | D03104 | 4 | | | 050-099 |
| 102 | 22 | PA | | | 10-0 | 33-21-32 | SM00014 | | 9 | | D03104 | 4 | | | 150-199, 275-299 |
| 103 | 22 | PA | | | 12-0 | 33-21-32 | D02164 | | 9 | | D03104 | 1 | | | 050-099 |
| 103 | 22 | PA | | | 14-0 | 33-21-32 | D02164 | | 9 | | D03104 | 1 | | | 150-199, 275-299 |
| 104 | 22 | PA | | | 12-0 | 33-21-32 | D02164 | | 10 | | D03104 | 2 | | | 050-099 |
| 104 | 22 | PA | | | 14-0 | 33-21-32 | D02164 | | 10 | | D03104 | 2 | | | 150-199, 275-299 |
| 105 | 22 | PA | | | 5-0 | 33-21-32 | D02164 | | 11 | | SM00013 | | 9 | | 050-099, 150-199, 275-278 |
| 105 | 22 | PA | | | 6-0 | 33-21-32 | D02164 | | 11 | | SM00013 | | 9 | | 280-299 |
| 106 | 22 | PA | | | 5-0 | 33-21-32 | D02164 | | 12 | | SM00014 | | 9 | | 050-099, 150-199, 275-278 |
| 106 | 22 | PA | | | 6-0 | 33-21-32 | D02164 | | 12 | | SM00014 | | 9 | | 280-299 |
| 109 | 20 | PA | | | 4-0 | 33-21-32 | GD01594 | S.. | E | | D02170 | 8 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 28

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | |
| 109 | 20 | | PA | 4-0 | 33-21-32 | GD04820 | S.. | E | | D02170 | | | 8 | | 150-199 | |
| 109 | 20 | | PA | 5-0 | 33-21-32 | GD04848 | S.. | E | | D02170 | | | 8 | | 275-278 | |
| 109 | 20 | | PA | 9-0 | 33-21-32 | GD04848 | S.. | E | | D02170 | | | 8 | | 280-299 | |
| 110 | 20 | | PA | 4-0 | 33-21-32 | GD01596 | A.. | E | | D02170 | | | 7 | | 050-099 | |
| 110 | 20 | | PA | 4-0 | 33-21-32 | GD04818 | A.. | E | | D02170 | | | 7 | | 150-154, 157-165, 167-199 | |
| 110 | 20 | | PQ | EJ | 4-0 | 33-21-32 | GD04818 | A.. | E | | D02170 | | 7 | | 155-156, 166 | |
| 110 | 20 | | PA | | 5-0 | 33-21-32 | GD04864 | A.. | E | | D02170 | | 7 | | 275-278 | |
| 110 | 20 | | PA | | 9-0 | 33-21-32 | GD04864 | A.. | E | | D02170 | | 7 | | 280-299 | |
| 110Z | | | | EJ | 0-0 | 33-21-32 | GD04818 | DED | | | D02170 | DED | | | 155-156, 166 | |
| 121 | 22 | | PA | | 19-0 | 33-21-32 | D02170 | | 2 | | D03194 | | 1 | | 050-099 | |
| 121 | 22 | | PA | | 25-0 | 33-21-32 | D02170 | | 2 | | D03194 | | 1 | | 150-199, 275-278 | |
| 121 | 22 | | PA | | 26-0 | 33-21-32 | D02170 | | 2 | | D03194 | | 1 | | 280-299 | |
| 122 | 22 | | PA | | 20-0 | 33-21-32 | D02170 | | 3 | | D03194 | | 2 | | 050-099 | |
| 122 | 22 | | PA | | 25-0 | 33-21-32 | D02170 | | 3 | | D03194 | | 2 | | 150-199, 275-278 | |
| 122 | 22 | | PA | | 26-0 | 33-21-32 | D02170 | | 3 | | D03194 | | 2 | | 280-299 | |
| 123 | 22 | | PA | | 18-0 | 33-21-32 | SM00017 | | 9 | | D03194 | | 3 | | 050-099 | |
| 123 | 22 | | PA | | 17-0 | 33-21-32 | SM00017 | | 9 | | D03194 | | 3 | | 150-199, 275-278 | |
| 123 | 22 | | PA | | 20-0 | 33-21-32 | SM00017 | | 9 | | D03194 | | 3 | | 280-299 | |
| 124 | 22 | | PA | | 18-0 | 33-21-32 | SM00018 | | 9 | | D03194 | | 4 | | 050-099 | |
| 124 | 22 | | PA | | 17-0 | 33-21-32 | SM00018 | | 9 | | D03194 | | 4 | | 150-199, 275-278 | |
| 124 | 22 | | PA | | 20-0 | 33-21-32 | SM00018 | | 9 | | D03194 | | 4 | | 280-299 | |
| 125 | 22 | | PA | | 9-0 | 33-21-32 | SM00017 | | 9 | | D03112 | | 3 | | 050-099, 280-299 | |
| 125 | 22 | | PA | | 10-0 | 33-21-32 | SM00017 | | 9 | | D03112 | | 3 | | 150-199, 275-278 | |
| 126 | 22 | | PA | | 9-0 | 33-21-32 | SM00018 | | 9 | | D03112 | | 4 | | 050-099, 280-299 | |
| 126 | 22 | | PA | | 10-0 | 33-21-32 | SM00018 | | 9 | | D03112 | | 4 | | 150-199, 275-278 | |
| 127 | 22 | | PA | | 13-0 | 33-21-32 | D02170 | | 9 | | D03112 | | 1 | | 050-099, 280-299 | |
| 127 | 22 | | PA | | 16-0 | 33-21-32 | D02170 | | 9 | | D03112 | | 1 | | 150-199 | |
| 127 | 22 | | PA | | 12-0 | 33-21-32 | D02170 | | 9 | | D03112 | | 1 | | 275-278 | |
| 128 | 22 | | PA | | 13-0 | 33-21-32 | D02170 | | 10 | | D03112 | | 2 | | 050-099, 280-299 | |
| 128 | 22 | | PA | | 16-0 | 33-21-32 | D02170 | | 10 | | D03112 | | 2 | | 150-199 | |
| 128 | 22 | | PA | | 12-0 | 33-21-32 | D02170 | | 10 | | D03112 | | 2 | | 275-278 | |
| 129 | 22 | | PA | | 6-0 | 33-21-32 | D02170 | | 11 | | SM00017 | | 9 | | 050-099 | |
| 129 | 22 | | PA | | 8-0 | 33-21-32 | D02170 | | 11 | | SM00017 | | 9 | | 150-199, 275-278 | |
| 129 | 22 | | PA | | 7-0 | 33-21-32 | D02170 | | 11 | | SM00017 | | 9 | | 280-299 | |
| 12A | 20 | | PA | | 23-0 | 33-21-32 | D02164 | | 5 | | SM00053 | | 9 | | 162-163 | |
| 12A | 20 | | PA | | 18-0 | 33-21-32 | D02164 | | 5 | | SM00053 | | 9 | | 164-165, 167-199 | |
| 12A | 20 | | PQ | AL | 18-0 | 33-21-32 | D02164 | | 5 | | SM00053 | | 9 | | 166 | |
| 12AZ | | | | AL | 0-0 | 33-21-32 | D02164 | DED | | | SM00053 | DED | | | 166 | |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 29

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | |
| 130 | 22 | | PA | | 6-0 | 33-21-32 | D02170 | | 12 | | SM00018 | | | | 9 | 050-099 |
| 130 | 22 | | PA | | 8-0 | 33-21-32 | D02170 | | 12 | | SM00018 | | | | 9 | 150-199, 275-278 |
| 130 | 22 | | PA | | 7-0 | 33-21-32 | D02170 | | 12 | | SM00018 | | | | 9 | 280-299 |
| 132 | 20 | | PA | | 3-0 | 33-21-32 | GD02202 | | S.. | E | D03100 | | | 5 | | 050-099, 150-199, 275-278 |
| 132 | 20 | | PA | | 4-0 | 33-21-32 | GD02202 | | S.. | E | D03100 | | | 5 | | 280-299 |
| 133 | 20 | | PA | | 3-0 | 33-21-32 | GD02042 | | S.. | E | D03186 | | | 5 | | 050-099, 150-199, 275-278 |
| 133 | 20 | | PA | | 4-0 | 33-21-32 | GD02042 | | S.. | E | D03186 | | | 5 | | 280-299 |
| 134 | 20 | | PA | | 3-0 | 33-21-32 | GD02206 | | S.. | E | D03104 | | | 5 | | 050-099, 150-199, 275-278 |
| 134 | 20 | | PA | | 4-0 | 33-21-32 | GD02206 | | S.. | E | D03104 | | | 5 | | 280-299 |
| 135 | 20 | | PA | | 4-0 | 33-21-32 | GD02214 | | S.. | E | D03112 | | | 5 | | 050-099, 280-299 |
| 135 | 20 | | PA | | 3-0 | 33-21-32 | GD02214 | | S.. | E | D03112 | | | 5 | | 150-199, 275-278 |
| 136 | 20 | | PA | | 3-0 | 33-21-32 | GD02050 | | S.. | E | D03194 | | | 5 | | 050-099, 150-199, 275-278 |
| 136 | 20 | | PA | | 4-0 | 33-21-32 | GD02050 | | S.. | E | D03194 | | | 5 | | 280-299 |
| 139 | 20 | | PA | | 3-0 | 33-21-32 | GD02046 | | S.. | E | D03190 | | | 5 | | 050-099, 150-199, 275-278 |
| 139 | 20 | | PA | | 4-0 | 33-21-32 | GD02046 | | S.. | E | D03190 | | | 5 | | 280-299 |
| 13A | 20 | | PA | | 15-0 | 33-21-32 | D10922 | | 5 | | SM00053 | | | 9 | | 162-163 |
| 13A | 20 | | PA | | 10-0 | 33-21-32 | D10922 | | 5 | | SM00053 | | | 9 | | 164-165, 167-199 |
| 13A | 20 | | PQ | AM | 10-0 | 33-21-32 | D10922 | | 5 | | SM00053 | | | 9 | | 166 |
| 13AZ | | | | AM | 0-0 | 33-21-32 | D10922 | | DED | | SM00053 | | DED | | | 166 |
| 140 | 20 | | PA | | 3-0 | 33-21-32 | GD02080 | | S.. | E | D03084 | | | 5 | | ALL |
| 141 | 20 | | PA | | 4-0 | 33-21-32 | GD02054 | | S.. | E | D03116 | | | 5 | | 050-099 |
| 141 | 20 | | PA | | 5-0 | 33-21-32 | D03116 | | 5 | | GD02054 | | S.. | E | | 150-199, 275-278 |
| 141 | 20 | | PA | | 4-0 | 33-21-32 | D03116 | | 5 | | GD02054 | | S.. | E | | 280-299 |
| 142 | 20 | | PA | | 3-0 | 33-21-34 | GD02084 | | S.. | E | D03088 | | | 5 | | 050-099 |
| 142 | 20 | | PA | | 3-0 | 33-21-34 | GD04650 | | S.. | E | D03088 | | | 5 | | 150-199, 275-278 |
| 142 | 20 | | PA | | 4-0 | 33-21-34 | GD04650 | | S.. | E | D03088 | | | 5 | | 280-299 |
| 143 | 20 | | PA | | 3-0 | 33-21-34 | GD02086 | | S.. | E | D03090 | | | 5 | | 050-099 |
| 143 | 20 | | PA | | 3-0 | 33-21-34 | GD02084 | | S.. | E | D03090 | | | 5 | | 275-299 |
| 144 | 20 | | PA | | 3-0 | 33-21-34 | GD02088 | | S.. | E | D03092 | | | 5 | | 050-099, 275-278 |
| 144 | 20 | | PA | | 4-0 | 33-21-34 | GD02088 | | S.. | E | D03092 | | | 5 | | 280-299 |
| 145 | 20 | | PA | | 4-0 | 33-21-34 | GD02062 | | S.. | E | D03124 | | | 5 | | 050-099 |
| 146 | 20 | | PA | | 4-0 | 33-21-34 | GD02092 | | S.. | E | D03096 | | | 5 | | 050-099, 280-299 |
| 146 | 20 | | PA | | 3-0 | 33-21-34 | GD02092 | | S.. | E | D03096 | | | 5 | | 150-199, 275-278 |
| 147 | 16 | | PA | | 58-0 | 33-21-12 | D05808P | | 1 | | D05112P | | | 19 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 30

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| 147 | 12 | | PA | 72-0 | 33-21-12 | D05808P | | 1 | | | | | D05112P | 19 | | | 150-199 |
| 147 | 12 | | PA | 69-0 | 33-21-12 | D05808P | | 1 | | | | | D05112P | 19 | | | 275-278 |
| 147 | 12 | | PA | 70-0 | 33-21-12 | D05808P | | 1 | | | | | D05112P | 19 | | | 280-299 |
| 148 | 16 | | PA | 58-0 | 33-21-12 | D05808P | | 2 | | | | | D05112P | 15 | | | 050-099 |
| 148 | 12 | | PA | 72-0 | 33-21-12 | D05808P | | 2 | | | | | D05112P | 15 | | | 150-199 |
| 148 | 12 | | PA | 69-0 | 33-21-12 | D05808P | | 2 | | | | | D05112P | 15 | | | 275-278 |
| 148 | 12 | | PA | 70-0 | 33-21-12 | D05808P | | 2 | | | | | D05112P | 15 | | | 280-299 |
| 149 | 24 | | PK | 69-0 | 33-21-12 | D05110P | | 5 | | | | | D05112P | 13 | | | 275-278 |
| 149 | 24 | | PK | 70-0 | 33-21-12 | D05110P | | 5 | | | | | D05112P | 13 | | | 280-299 |
| 14A | 22 | | PA | 19-0 | 33-21-32 | D10922 | | 11 | | | | | D03102 | 3 | | | 162-163 |
| 14A | 22 | | PA | 14-0 | 33-21-32 | D10922 | | 11 | | | | | D03102 | 3 | | | 164-199 |
| 150 | 24 | | PK | 59-0 | 33-21-12 | D05110P | | 14 | | | | | D05112P | 14 | | | 050-099 |
| 150 | 24 | | PK | 72-0 | 33-21-12 | D05110P | | 14 | | | | | D05112P | 14 | | | 150-199 |
| 150 | 24 | | PK | 69-0 | 33-21-12 | D05110P | | 14 | | | | | D05112P | 14 | | | 275-278 |
| 150 | 24 | | PK | 70-0 | 33-21-12 | D05110P | | 14 | | | | | D05112P | 14 | | | 280-299 |
| 151 | 24 | | PK | 69-0 | 33-21-12 | D05110P | | 23 | | | | | D05112P | 22 | | | 275-278 |
| 151 | 24 | | PK | 70-0 | 33-21-12 | D05110P | | 23 | | | | | D05112P | 22 | | | 280-299 |
| 152 | 20 | | PA | 21-0 | 33-21-11 | D02690 | | 2 | | | | | SP00886 | | 9 | | 275-278 |
| 152 | 20 | | PA | 20-0 | 33-21-11 | D02690 | | 2 | | | | | SP00886 | | 9 | | 280-299 |
| 153 | 20 | | PA | 21-0 | 33-21-11 | D02690 | | 3 | | | | | SP00888 | | 9 | | 275-278 |
| 153 | 20 | | PA | 20-0 | 33-21-11 | D02690 | | 3 | | | | | SP00888 | | 9 | | 280-299 |
| 154 | 20 | | PA | 9-0 | 33-21-11 | D02690 | | 5 | | | | | D05110P | | 2 | | 275-299 |
| 155 | 20 | | PA | 9-0 | 33-21-11 | D02690 | | 7 | | | | | GD01022 | A.. | E | | 275-299 |
| 156 | 20 | | PA | 9-0 | 33-21-11 | D02690 | | 8 | | | | | GD01582 | S.. | E | | 275-299 |
| 157 | 20 | | PA | 13-0 | 33-21-11 | D02690 | | 9 | | | | | SP00862 | | 9 | | 275-278 |
| 157 | 20 | | PA | 14-0 | 33-21-11 | D02690 | | 9 | | | | | SP00862 | | 9 | | 280-299 |
| 158 | 20 | | PA | 13-0 | 33-21-11 | D02690 | | 10 | | | | | SP00864 | | 9 | | 275-278 |
| 158 | 20 | | PA | 14-0 | 33-21-11 | D02690 | | 10 | | | | | SP00864 | | 9 | | 280-299 |
| 159 | 20 | | PA | 11-0 | 33-21-11 | D02690 | | 11 | | | | | SP00866 | | 9 | | 275-299 |
| 15A | 22 | | PA | 19-0 | 33-21-32 | D10922 | | 12 | | | | | D03102 | | 4 | | 162-163 |
| 15A | 22 | | PA | 14-0 | 33-21-32 | D10922 | | 12 | | | | | D03102 | | 4 | | 164-199 |
| 160 | 20 | | PA | 11-0 | 33-21-11 | D02690 | | 12 | | | | | SP00868 | | 9 | | 275-299 |
| 161 | 20 | | PA | 6-0 | 33-21-11 | L00236 | | = G | E | | | | GD01582 | S.. | E | | 275-278 |
| 161 | 20 | | PA | 5-0 | 33-21-11 | L00236 | | = G | E | | | | GD01582 | S.. | E | | 280-299 |
| 162 | 20 | | PA | 13-0 | 33-21-11 | L00237 | | = G | E | | | | GD02730 | S.. | E | | 275-278 |
| 162 | 20 | | PA | 6-0 | 33-21-11 | L00237 | | = G | E | | | | GD02730 | S.. | E | | 280-299 |
| 163 | 20 | | PA | 31-0 | 33-21-11 | SP00858 | | | | 9 | | | SP00866 | | 9 | | 275-278 |
| 163 | 20 | | PA | 25-0 | 33-21-11 | SP00858 | | | | 9 | | | SP00866 | | 9 | | 280-299 |
| 164 | 20 | | PA | 31-0 | 33-21-11 | SP00860 | | | | 9 | | | SP00868 | | 9 | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 31

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| 164 | 20 | | PA | 25-0 | 33-21-11 | SP00860 | | | 9 | | | | SP00868 | | 9 | | 280-299 |
| 166 | 20 | | PA | 31-0 | 33-21-11 | D02692 | | | 2 | | | | SP00874 | | 9 | | 050-099 |
| 166 | 20 | | PA | 19-0 | 33-21-11 | D02692 | | | 2 | | | | SP00874 | | 9 | | 150-199, 275-278 |
| 166 | 20 | | PA | 20-0 | 33-21-11 | D02692 | | | 2 | | | | SP00874 | | 9 | | 280-299 |
| 167 | 20 | | PA | 31-0 | 33-21-11 | D02692 | | | 3 | | | | SP00876 | | 9 | | 050-099 |
| 167 | 20 | | PA | 19-0 | 33-21-11 | D02692 | | | 3 | | | | SP00876 | | 9 | | 150-199, 275-278 |
| 167 | 20 | | PA | 20-0 | 33-21-11 | D02692 | | | 3 | | | | SP00876 | | 9 | | 280-299 |
| 168 | 20 | | PA | 16-0 | 33-21-11 | D02692 | | | 5 | | | | D05110P | 17 | | | ALL |
| 169 | 20 | | PA | 9-0 | 33-21-11 | D02692 | | | 7 | | | | GD01588 | A.. | E | | 050-099, 280-299 |
| 169 | 20 | | PA | 8-0 | 33-21-11 | D02692 | | | 7 | | | | GD01588 | A.. | E | | 150-199, 275-278 |
| 16A | 22 | | PA | 19-0 | 33-21-32 | D10922 | | | 9 | | | | D03102 | 1 | | | 162-163 |
| 16A | 22 | | PA | 14-0 | 33-21-32 | D10922 | | | 9 | | | | D03102 | 1 | | | 164-199 |
| 170 | 20 | | PA | 9-0 | 33-21-11 | D02692 | | | 8 | | | | GD01586 | S.. | E | | 050-099, 280-299 |
| 170 | 20 | | PA | 8-0 | 33-21-11 | D02692 | | | 8 | | | | GD01586 | S.. | E | | 150-199, 275-278 |
| 171 | 20 | | PA | 14-0 | 33-21-11 | D02692 | | | 9 | | | | SP00878 | | 9 | | 050-099, 150-199, 275-278 |
| 171 | 20 | | PA | 13-0 | 33-21-11 | D02692 | | | 9 | | | | SP00878 | | 9 | | 280-299 |
| 172 | 20 | | PA | 14-0 | 33-21-11 | D02692 | | | 10 | | | | SP00880 | | 9 | | 050-099, 150-199, 275-278 |
| 172 | 20 | | PA | 13-0 | 33-21-11 | D02692 | | | 10 | | | | SP00880 | | 9 | | 280-299 |
| 173 | 20 | | PA | 10-0 | 33-21-11 | D02692 | | | 11 | | | | SP00882 | | 9 | | 050-099 |
| 173 | 20 | | PA | 26-0 | 33-21-11 | D02692 | | | 11 | | | | SP00882 | | 9 | | 150-199 |
| 173 | 20 | | PA | 11-0 | 33-21-11 | D02692 | | | 11 | | | | SP00882 | | 9 | | 275-299 |
| 174 | 20 | | PA | 10-0 | 33-21-11 | D02692 | | | 12 | | | | SP00884 | | 9 | | 050-099 |
| 174 | 20 | | PA | 26-0 | 33-21-11 | D02692 | | | 12 | | | | SP00884 | | 9 | | 150-199 |
| 174 | 20 | | PA | 11-0 | 33-21-11 | D02692 | | | 12 | | | | SP00884 | | 9 | | 275-299 |
| 175 | 20 | | PA | 5-0 | 33-21-11 | L00238 | | =G | E | | | | GD01586 | S.. | E | | 050-099, 280-299 |
| 175 | 20 | | PA | 6-0 | 33-21-11 | L00238 | | =G | E | | | | GD01586 | S.. | E | | 150-199, 275-278 |
| 176 | 20 | | PA | 15-0 | 33-21-11 | L00239 | | =G | E | | | | GD00938 | S.. | 2 | | 050-099 |
| 176 | 20 | | PA | 10-0 | 33-21-11 | L00239 | | =G | E | | | | GD00938 | S.. | 2 | | 150-199, 275-278 |
| 176 | 20 | | PA | 9-0 | 33-21-11 | L00239 | | =G | E | | | | GD00938 | S.. | 2 | | 280-299 |
| 177 | 20 | | PA | 38-0 | 33-21-11 | SP00870 | | | 9 | | | | SP00882 | | 9 | | 050-099 |
| 177 | 20 | | PA | 28-0 | 33-21-11 | SP00870 | | | 9 | | | | SP00882 | | 9 | | 150-199, 275-278 |
| 177 | 20 | | PA | 29-0 | 33-21-11 | SP00870 | | | 9 | | | | SP00882 | | 9 | | 280-299 |
| 178 | 20 | | PA | 38-0 | 33-21-11 | SP00872 | | | 9 | | | | SP00884 | | 9 | | 050-099 |
| 178 | 20 | | PA | 28-0 | 33-21-11 | SP00872 | | | 9 | | | | SP00884 | | 9 | | 150-199, 275-278 |
| 178 | 20 | | PA | 29-0 | 33-21-11 | SP00872 | | | 9 | | | | SP00884 | | 9 | | 280-299 |
| 179 | 20 | | PA | 22-0 | 33-21-11 | D02694 | | | 2 | | | | SP00792 | | 9 | | 050-099 |
| 179 | 20 | | PA | 19-0 | 33-21-11 | D02694 | | | 2 | | | | SP00792 | | 9 | | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 32

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|-----|----|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | | | |
| 179 | 20 | | PA | 21-0 | 33-21-11 | D02694 | | | | | 2 | | | | SP00792 | | 9 | | 280-299 |
| 17A | 22 | | PA | 19-0 | 33-21-32 | D10922 | | | | | 10 | | | | D03102 | | 2 | | 162-163 |
| 17A | 22 | | PA | 14-0 | 33-21-32 | D10922 | | | | | 10 | | | | D03102 | | 2 | | 164-199 |
| 180 | 20 | | PA | 22-0 | 33-21-11 | D02694 | | | | | 3 | | | | SP00794 | | 9 | | 050-099 |
| 180 | 20 | | PA | 19-0 | 33-21-11 | D02694 | | | | | 3 | | | | SP00794 | | 9 | | 150-199, 275-278 |
| 180 | 20 | | PA | 21-0 | 33-21-11 | D02694 | | | | | 3 | | | | SP00794 | | 9 | | 280-299 |
| 181 | 20 | | PA | 13-0 | 33-21-11 | D02694 | | | | | 5 | | | | SM00030 | | 9 | | 050-099 |
| 181 | 20 | | PA | 23-0 | 33-21-11 | D02694 | | | | | 5 | | | | D05110P | | 18 | | 150-199, 275-299 |
| 182 | 20 | | PA | 9-0 | 33-21-11 | D02694 | | | | | 7 | | | | GD01010 | A.. | E | | ALL |
| 183 | 20 | | PA | 9-0 | 33-21-11 | D02694 | | | | | 8 | | | | GD01546 | S.. | E | | ALL |
| 184 | 20 | | PA | 14-0 | 33-21-11 | D02694 | | | | | 9 | | | | SP00796 | | 9 | | 050-099, 150-199, 275-278 |
| 184 | 20 | | PA | 15-0 | 33-21-11 | D02694 | | | | | 9 | | | | SP00796 | | 9 | | 280-299 |
| 185 | 20 | | PA | 14-0 | 33-21-11 | D02694 | | | | | 10 | | | | SP00798 | | 9 | | 050-099, 150-199, 275-278 |
| 185 | 20 | | PA | 15-0 | 33-21-11 | D02694 | | | | | 10 | | | | SP00798 | | 9 | | 280-299 |
| 186 | 20 | | PA | 12-0 | 33-21-11 | D02694 | | | | | 11 | | | | SP00800 | | 9 | | 050-099, 150-199, 275-278 |
| 186 | 20 | | PA | 11-0 | 33-21-11 | D02694 | | | | | 11 | | | | SP00800 | | 9 | | 280-299 |
| 187 | 20 | | PA | 12-0 | 33-21-11 | D02694 | | | | | 12 | | | | SP00802 | | 9 | | 050-099, 150-199, 275-278 |
| 187 | 20 | | PA | 11-0 | 33-21-11 | D02694 | | | | | 12 | | | | SP00802 | | 9 | | 280-299 |
| 188 | 20 | | PA | 6-0 | 33-21-11 | L00244 | | | | | = G | E | | | GD01546 | S.. | E | | 050-099, 150-199, 275-278 |
| 188 | 20 | | PA | 4-0 | 33-21-11 | L00244 | | | | | = G | E | | | GD01546 | S.. | E | | 280-299 |
| 189 | 20 | | PA | 5-0 | 33-21-11 | L00246 | | | | | = G | E | | | GD02608 | S.. | E | | 050-099, 150-199, 275-278 |
| 189 | 20 | | PA | 7-0 | 33-21-11 | L00246 | | | | | = G | E | | | GD02608 | S.. | E | | 280-299 |
| 18A | 20 | | PA | 15-0 | 33-21-32 | GD01582 | | | | | S.. | E | | | D03102 | | 5 | | 162-163 |
| 18A | 20 | | PA | 10-0 | 33-21-32 | GD01582 | | | | | S.. | E | | | D03102 | | 5 | | 164-199 |
| 190 | 20 | | PA | 29-0 | 33-21-11 | SP00788 | | | | | | 9 | | | SP00800 | | 9 | | 050-099, 150-199, 275-278 |
| 190 | 20 | | PA | 30-0 | 33-21-11 | SP00788 | | | | | | 9 | | | SP00800 | | 9 | | 280-299 |
| 191 | 20 | | PA | 29-0 | 33-21-11 | SP00790 | | | | | | 9 | | | SP00802 | | 9 | | 050-099, 150-199, 275-278 |
| 191 | 20 | | PA | 30-0 | 33-21-11 | SP00790 | | | | | | 9 | | | SP00802 | | 9 | | 280-299 |
| 192 | 20 | | PA | 23-0 | 33-21-11 | D02696 | | | | | 2 | | | | SP00808 | | 9 | | 050-099 |
| 192 | 20 | | PA | 26-0 | 33-21-13 | D02696 | | | | | 2 | | | | SP00808 | | 9 | | 150-199 |
| 192 | 20 | | PA | 23-0 | 33-21-13 | D02696 | | | | | 2 | | | | SP00808 | | 9 | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 33

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| 192 | 20 | | PA | 14-0 | 33-21-13 | D02696 | | 2 | | | | | SM00066 | | 9 | | 280-299 |
| 193 | 20 | | PA | 23-0 | 33-21-11 | D02696 | | 3 | | | | | SP00810 | | 9 | | 050-099 |
| 193 | 20 | | PA | 26-0 | 33-21-13 | D02696 | | 3 | | | | | SP00810 | | 9 | | 150-199 |
| 193 | 20 | | PA | 23-0 | 33-21-13 | D02696 | | 3 | | | | | SP00810 | | 9 | | 275-278 |
| 193 | 20 | | PA | 14-0 | 33-21-13 | D02696 | | 3 | | | | | SM00065 | | 9 | | 280-299 |
| 194 | 20 | | PA | 16-0 | 33-21-11 | D02696 | | 5 | | | | | SM00030 | | 9 | | 050-099 |
| 194 | 20 | | PA | 33-0 | 33-21-13 | D02696 | | 5 | | | | | D05110P | 16 | | | 150-199 |
| 194 | 20 | | PA | 32-0 | 33-21-13 | D02696 | | 5 | | | | | D05112P | 20 | | | 275-278 |
| 194 | 20 | | PA | 1-0 | 33-21-13 | D02696 | | 5 | | | | | SM00073 | | 9 | | 280-299 |
| 195 | 20 | | PA | 9-0 | 33-21-11 | D02696 | | 7 | | | | | GD01596 | A.. | E | | 050-099 |
| 195 | 20 | | PA | 13-0 | 33-21-13 | D02696 | | 7 | | | | | GD04868 | A.. | E | | 150-199 |
| 195 | 20 | | PA | 4-0 | 33-21-13 | D02696 | | 7 | | | | | GD04818 | A.. | E | | 275-278 |
| 195 | 20 | | PA | 5-0 | 33-21-13 | D02696 | | 7 | | | | | GD04842 | A.. | E | | 280-299 |
| 196 | 20 | | PA | 16-0 | 33-21-11 | D02696 | | 8 | | | | | GD01594 | S.. | E | | 050-099 |
| 196 | 20 | | PA | 13-0 | 33-21-13 | D02696 | | 8 | | | | | GD04850 | S.. | E | | 150-199 |
| 196 | 20 | | PA | 4-0 | 33-21-13 | D02696 | | 8 | | | | | GD04820 | S.. | E | | 275-278 |
| 196 | 20 | | PA | 5-0 | 33-21-13 | D02696 | | 8 | | | | | GD04844 | S.. | E | | 280-299 |
| 197 | 20 | | PA | 14-0 | 33-21-11 | D02696 | | 9 | | | | | SP00812 | | 9 | | 050-099 |
| 197 | 20 | | PA | 19-0 | 33-21-13 | D02696 | | 9 | | | | | SP00812 | | 9 | | 150-199 |
| 197 | 20 | | PA | 13-0 | 33-21-13 | D02696 | | 9 | | | | | SP00812 | | 9 | | 275-278 |
| 197 | 20 | | PA | 6-0 | 33-21-13 | D02696 | | 9 | | | | | SM00069 | | 9 | | 280-299 |
| 198 | 20 | | PA | 14-0 | 33-21-11 | D02696 | | 10 | | | | | SP00814 | | 9 | | 050-099 |
| 198 | 20 | | PA | 19-0 | 33-21-13 | D02696 | | 10 | | | | | SP00814 | | 9 | | 150-199 |
| 198 | 20 | | PA | 13-0 | 33-21-13 | D02696 | | 10 | | | | | SP00814 | | 9 | | 275-278 |
| 198 | 20 | | PA | 6-0 | 33-21-13 | D02696 | | 10 | | | | | SM00070 | | 9 | | 280-299 |
| 199 | 20 | | PA | 14-0 | 33-21-11 | D02696 | | 11 | | | | | SP00816 | | 9 | | 050-099 |
| 199 | 20 | | PA | 16-0 | 33-21-13 | D02696 | | 11 | | | | | SP00816 | | 9 | | 150-199 |
| 199 | 20 | | PA | 12-0 | 33-21-13 | D02696 | | 11 | | | | | SP00816 | | 9 | | 275-278 |
| 199 | 20 | | PA | 7-0 | 33-21-13 | D02696 | | 11 | | | | | SM00067 | | 9 | | 280-299 |
| 21A | 20 | | PA | 15-0 | 33-21-32 | GD01582 | | | | | | | D10922 | | 8 | | 162-163 |
| 21A | 20 | | PA | 10-0 | 33-21-32 | GD01582 | | | | | | | D10922 | | 8 | | 164-199 |
| 22A | 20 | | PA | 15-0 | 33-21-32 | GD01022 | | | | | | * | D10922 | | 7 | | 162-163 |
| 22A | 20 | | PA | 10-0 | 33-21-32 | GD01022 | | | | | | * | D10922 | | 7 | | 164-165, 167-199 |
| 22A | 20 | | PQ | 10-0 | 33-21-32 | GD01022 | | | | | | * | D10922 | | 7 | | 166 |
| 22AZ | | | AV | 0-0 | 33-21-32 | GD01022 | | | | | | | D10922 | DED | | | 166 |
| 501 | 20 | | PA | 14-0 | 33-21-11 | D02696 | | 12 | | | | | SP00818 | | 9 | | 050-099 |
| 501 | 20 | | PA | 16-0 | 33-21-13 | D02696 | | 12 | | | | | SP00818 | | 9 | | 150-199 |
| 501 | 20 | | PA | 12-0 | 33-21-13 | D02696 | | 12 | | | | | SP00818 | | 9 | | 275-278 |
| 501 | 20 | | PA | 7-0 | 33-21-13 | D02696 | | 12 | | | | | SM00068 | | 9 | | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 34
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|--------|-------|------|----------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| 502 | 20 | | PA | 8-0 | 33-21-11 | L00245 | =G | E | | | | | GD01594 | S.. | E | | 050-099 |
| 502 | 20 | | PA | 30-0 | 33-21-13 | L00245 | =G | E | | | | | GD04872 | S.. | E | | 150-199 |
| 502 | 20 | | PA | 17-0 | 33-21-13 | L00245 | =G | E | | | | | GD04822 | S.. | E | | 275-278 |
| 502 | 20 | | PA | 7-0 | 33-21-13 | SM00056 | | 9 | | | | | GD04848 | S.. | E | | 280-299 |
| 503 | 20 | | PA | 4-0 | 33-21-11 | L00247 | =G | E | | | | | GD02696 | S.. | E | | 050-099 |
| 503 | 20 | | PA | 14-0 | 33-21-13 | L00247 | =G | E | | | | | GD04872 | S.. | E | | 150-199 |
| 503 | 20 | | PA | 5-0 | 33-21-13 | L00247 | =G | E | | | | | GD04824 | S.. | E | | 275-278 |
| 503 | 20 | | PA | 5-0 | 33-21-13 | SM00055 | | 9 | | | | | GD04846 | S.. | E | | 280-299 |
| 504 | 20 | | PA | 31-0 | 33-21-11 | SP00804 | | 9 | | | | | SP00816 | | 9 | | 050-099 |
| 504 | 20 | | PA | 28-0 | 33-21-13 | SP00804 | | 9 | | | | | SP00816 | | 9 | | 150-199, 275-278 |
| 504 | 20 | | PA | 10-0 | 33-21-13 | SM00063 | | 9 | | | | | SP00816 | | 9 | | 280-299 |
| 505 | 20 | | PA | 31-0 | 33-21-11 | SP00806 | | 9 | | | | | SP00818 | | 9 | | 050-099 |
| 505 | 20 | | PA | 28-0 | 33-21-13 | SP00806 | | 9 | | | | | SP00818 | | 9 | | 150-199, 275-278 |
| 505 | 20 | | PA | 9-0 | 33-21-13 | SM00064 | | 9 | | | | | SP00818 | | 9 | | 280-299 |
| 599 | 20 | | PA | 59-0 | 33-26-11 | D05110P | | 43 | | | | | D05112P | | 16 | | 050-099 |
| 632 | 20 | | PA | 14-0 | 33-21-11 | D11160 | | 2 | | | | | SP02796 | | 9 | | 150-199, 275-278 |
| 632 | 20 | | PA | 15-0 | 33-21-11 | D11160 | | 2 | | | | | STA0654L | CAP | Y | | 280-299 |
| 633 | 20 | | PA | 14-0 | 33-21-11 | D11160 | | 3 | | | | | SP02798 | | 9 | | 150-199, 275-278 |
| 633 | 20 | | PA | 15-0 | 33-21-11 | D11160 | | 3 | | | | | STA0654L | CAP | Y | | 280-299 |
| 634 | 20 | | PA | 5-0 | 33-21-11 | D11160 | | 7 | | | | | GD04838 | A.. | E | | 150-199, 275-278 |
| 634 | 20 | | PA | 4-0 | 33-21-11 | D11160 | | 7 | | | | | GD04838 | A.. | E | | 280-299 |
| 635 | 20 | | PA | 5-0 | 33-21-11 | D11160 | | 8 | | | | | GD04840 | S.. | E | | 150-199, 275-278 |
| 635 | 20 | | PA | 4-0 | 33-21-11 | D11160 | | 8 | | | | | GD04840 | S.. | E | | 280-299 |
| 636 | 20 | | PA | 30-0 | 33-21-11 | D11160 | | 5 | | | | | D05110P | | 13 | | 150-199, 275-299 |
| 637 | 20 | | PA | 24-0 | 33-21-11 | D11160 | | 11 | | | | | SP02842 | | 9 | | 150-199, 275-299 |
| 638 | 20 | | PA | 24-0 | 33-21-11 | D11160 | | 12 | | | | | SP02840 | | 9 | | 150-199, 275-299 |
| 639 | 20 | | PA | 28-7 | 33-21-11 | D11160 | | 9 | | | | | SP02810 | | 9 | | 150-199, 275-278 |
| 639 | 20 | | PA | 36-0 | 33-21-11 | D11160 | | 9 | | | | | STA0654R | CAP | Y | | 280-299 |
| 640 | 20 | | PA | 28-7 | 33-21-11 | D11160 | | 10 | | | | | SP02812 | | 9 | | 150-199, 275-278 |
| 640 | 20 | | PA | 36-0 | 33-21-11 | D11160 | | 10 | | | | | STA0654R | CAP | Y | | 280-299 |
| 641 | 20 | | PA | 41-0 | 33-21-11 | D05112P | | 27 | | | | | SM00041 | | 9 | | 150-199 |
| 641 | 20 | | PA | 28-0 | 33-21-11 | D05112P | | 27 | | | | | SM00041 | | 9 | | 280-299 |
| 642 | 20 | | PA | 5-0 | 33-21-11 | L00764 | =G | E | | | | | GD04822 | S.. | E | | 150-199 |
| 642 | 20 | | PA | 9-0 | 33-21-11 | L00760 | =G | E | | | | | GD04848 | S.. | E | | 275-278 |
| 642 | 20 | | PA | 11-0 | 33-21-11 | STA0743L | | CAP | Y | | | | GD04822 | S.. | E | | 280-299 |
| 643 | 20 | | PA | 22-0 | 33-21-11 | D11164 | | 2 | | | | | SP02800 | | 9 | | 150-199 |
| 643 | 20 | | PA | 14-0 | 33-21-11 | D11164 | | 2 | | | | | SP02800 | | 9 | | 275-278 |
| 643 | 20 | | PA | 11-0 | 33-21-11 | D11164 | | 2 | | | | | ST0675L | CAP | Y | | 280-299 |
| 644 | 20 | | PA | 22-0 | 33-21-11 | D11164 | | 3 | | | | | SP02802 | | 9 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 35

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|----------|-------|------|------|--------|-------|------|------|----------|-------------|----|--|--|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | | | | |
| 644 | 20 | PA | | | 14-0 | 33-21-11 | D11164 | | 3 | | | | | | SP02802 | | 9 | | | 275-278 |
| 644 | 20 | PA | | | 11-0 | 33-21-11 | D11164 | | 3 | | | | | | ST0675L | CAP | Y | | | 280-299 |
| 645 | 20 | PA | | | 30-0 | 33-21-11 | D11164 | | 9 | | | | | | SP02804 | | 9 | | | 150-199 |
| 645 | 20 | PA | | | 19-0 | 33-21-11 | D11164 | | 9 | | | | | | SP02804 | | 9 | | | 275-278 |
| 645 | 20 | PA | | | 30-0 | 33-21-11 | D11164 | | 9 | | | | | | ST0675R | CAP | Y | | | 280-299 |
| 646 | 20 | PA | | | 30-0 | 33-21-11 | D11164 | | 10 | | | | | | SP02806 | | 9 | | | 150-199 |
| 646 | 20 | PA | | | 19-0 | 33-21-11 | D11164 | | 10 | | | | | | SP02806 | | 9 | | | 275-278 |
| 646 | 20 | PA | | | 30-0 | 33-21-11 | D11164 | | 10 | | | | | | ST0675R | CAP | Y | | | 280-299 |
| 647 | 20 | PA | | | 6-0 | 33-21-11 | L00757 | =G | | E | | | | | GD01618 | S.. | E | | | 150-199, 275-278 |
| 647 | 20 | PA | | | 9-0 | 33-21-11 | STA0654R | CAP | | Y | | | | | GD04824 | S.. | E | | | 280-299 |
| 648 | 20 | PA | | | 19-0 | 33-21-11 | D11164 | | 5 | | | | | | SM00041 | | 9 | | | 150-199 |
| 648 | 20 | PA | | | 37-0 | 33-21-11 | D11164 | | 5 | | | | | | D05110P | | 12 | | | 275-278 |
| 648 | 20 | PA | | | 39-0 | 33-21-11 | D11164 | | 5 | | | | | | D05110P | | 12 | | | 280-299 |
| 649 | 20 | PA | | | 17-0 | 33-21-11 | D11168 | | 5 | | | | | | SM00041 | | 9 | | | 150-199 |
| 649 | 20 | PA | | | 6-0 | 33-21-11 | D11168 | | 5 | | | | | | SM00041 | | 9 | | | 280-299 |
| 650 | 20 | PA | | | 15-0 | 33-21-11 | D11168 | | 3 | | | | | | SP02814 | | 9 | | | 150-199 |
| 650 | 20 | PA | | | 5-0 | 33-21-11 | D11168 | | 3 | | | | | | STA0743L | CAP | Y | | | 280-299 |
| 651 | 20 | PA | | | 15-0 | 33-21-11 | D11168 | | 2 | | | | | | SP02816 | | 9 | | | 150-199 |
| 651 | 20 | PA | | | 5-0 | 33-21-11 | D11168 | | 2 | | | | | | STA0743L | CAP | Y | | | 280-299 |
| 652 | 20 | PA | | | 30-0 | 33-21-11 | D11168 | | 9 | | | | | | SP02818 | | 9 | | | 150-199 |
| 652 | 20 | PA | | | 26-0 | 33-21-11 | D11168 | | 9 | | | | | | STA0743R | CAP | Y | | | 280-299 |
| 653 | 20 | PA | | | 30-0 | 33-21-11 | D11168 | | 10 | | | | | | SP02820 | | 9 | | | 150-199 |
| 653 | 20 | PA | | | 26-0 | 33-21-11 | D11168 | | 10 | | | | | | STA0743R | CAP | Y | | | 280-299 |
| 654 | 20 | PA | | | 3-0 | 33-21-32 | D03108 | | 5 | | | | | | GD02210 | S.. | E | | | 050-099 |
| 654 | 20 | PA | | | 4-0 | 33-21-32 | D03108 | | 5 | | | | | | GD02210 | S.. | E | | | 150-199, 275-299 |
| 655 | 22 | PA | | | 12-0 | 33-21-32 | D02168 | | 9 | | | | | | D03108 | | 1 | | | 050-099 |
| 655 | 22 | PA | | | 15-0 | 33-21-32 | D02168 | | 9 | | | | | | D03108 | | 1 | | | 150-199, 275-278 |
| 655 | 22 | PA | | | 13-0 | 33-21-32 | D02168 | | 9 | | | | | | D03108 | | 1 | | | 280-299 |
| 656 | 22 | PA | | | 12-0 | 33-21-32 | D02168 | | 10 | | | | | | D03108 | | 2 | | | 050-099 |
| 656 | 22 | PA | | | 15-0 | 33-21-32 | D02168 | | 10 | | | | | | D03108 | | 2 | | | 150-199, 275-278 |
| 656 | 22 | PA | | | 13-0 | 33-21-32 | D02168 | | 10 | | | | | | D03108 | | 2 | | | 280-299 |
| 657 | 22 | PA | | | 8-0 | 33-21-32 | D03108 | | 3 | | | | | | SM00037 | | 9 | | | 050-099, 150-199, 275-278 |
| 657 | 22 | PA | | | 10-0 | 33-21-32 | D03108 | | 3 | | | | | | SM00037 | | 9 | | | 280-299 |
| 658 | 22 | PA | | | 8-0 | 33-21-32 | D03108 | | 4 | | | | | | SM00038 | | 9 | | | 050-099, 150-199, 275-278 |
| 658 | 22 | PA | | | 10-0 | 33-21-32 | D03108 | | 4 | | | | | | SM00038 | | 9 | | | 280-299 |
| 659 | 22 | PA | | | 19-0 | 33-21-32 | D03190 | | 3 | | | | | | SM00037 | | 9 | | | 050-099, 150-199, 275-278 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 36
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| 659 | 22 | | PA | 17-0 | 33-21-32 | D03190 | | | 3 | | | | SM00037 | | 9 | | 280-299 |
| 660 | 22 | | PA | 19-0 | 33-21-32 | D03190 | | | 4 | | | | SM00038 | | 9 | | 050-099, 150-199, 275-278 |
| 660 | 22 | | PA | 17-0 | 33-21-32 | D03190 | | | 4 | | | | SM00038 | | 9 | | 280-299 |
| 661 | 22 | | PA | 7-0 | 33-21-34 | D02002 | | | 11 | | | | SM00039 | | 9 | | ALL |
| 662 | 22 | | PA | 7-0 | 33-21-34 | D02002 | | | 12 | | | | SM00040 | | 9 | | ALL |
| 663 | 22 | | PA | 21-0 | 33-21-34 | D03128 | | | 3 | | | | SM00039 | | 9 | | 050-099 |
| 663 | 22 | | PA | 23-0 | 33-21-34 | D03128 | | | 3 | | | | SM00039 | | 9 | | 150-199 |
| 663 | 22 | | PA | 21-1 | 33-21-34 | D03128 | | | 3 | | | | SM00039 | | 9 | | 275-299 |
| 664 | 22 | | PA | 21-0 | 33-21-34 | D03128 | | | 4 | | | | SM00040 | | 9 | | 050-099 |
| 664 | 22 | | PA | 23-0 | 33-21-34 | D03128 | | | 4 | | | | SM00040 | | 9 | | 150-199 |
| 664 | 22 | | PA | 21-1 | 33-21-34 | D03128 | | | 4 | | | | SM00040 | | 9 | | 275-299 |
| 665 | 22 | | PA | 24-0 | 33-21-34 | D03128 | | | 1 | | | | D02002 | | 9 | | 050-099 |
| 665 | 22 | | PA | 25-0 | 33-21-34 | D03128 | | | 1 | | | | D02002 | | 9 | | 150-199 |
| 665 | 22 | | PA | 23-6 | 33-21-34 | D03128 | | | 1 | | | | D02002 | | 9 | | 275-278 |
| 665 | 22 | | PA | 26-0 | 33-21-34 | D03128 | | | 1 | | | | D02002 | | 9 | | 280-299 |
| 666 | 22 | | PA | 24-0 | 33-21-34 | D03128 | | | 2 | | | | D02002 | | 10 | | 050-099 |
| 666 | 22 | | PA | 25-0 | 33-21-34 | D03128 | | | 2 | | | | D02002 | | 10 | | 150-199 |
| 666 | 22 | | PA | 23-6 | 33-21-34 | D03128 | | | 2 | | | | D02002 | | 10 | | 275-278 |
| 666 | 22 | | PA | 26-0 | 33-21-34 | D03128 | | | 2 | | | | D02002 | | 10 | | 280-299 |
| 667 | 20 | | PA | 4-0 | 33-21-34 | D03128 | | | 5 | | | | GD02066 | S.. | E | | 050-099, 280-299 |
| 667 | 20 | | PA | 3-0 | 33-21-34 | D03128 | | | 5 | | | | GD02066 | S.. | E | | 150-199 |
| 667 | 20 | | PA | 2-11 | 33-21-34 | D03128 | | | 5 | | | | GD02066 | S.. | E | | 275-278 |
| 670 | 20 | | PA | 23-0 | 33-21-13 | D02698 | | | 2 | | | | SP01330 | | 9 | | 050-099 |
| 670 | 20 | | PA | 27-0 | 33-21-13 | D02698 | | | 2 | | | | SP01330 | | 9 | | 150-199, 275-278 |
| 670 | 20 | | PA | 28-0 | 33-21-13 | D02698 | | | 2 | | | | SP01330 | | 9 | | 280-299 |
| 671 | 20 | | PA | 23-0 | 33-21-13 | D02698 | | | 3 | | | | SP01332 | | 9 | | 050-099 |
| 671 | 20 | | PA | 27-0 | 33-21-13 | D02698 | | | 3 | | | | SP01332 | | 9 | | 150-199, 275-278 |
| 671 | 20 | | PA | 28-0 | 33-21-13 | D02698 | | | 3 | | | | SP01332 | | 9 | | 280-299 |
| 672 | 20 | | PA | 7-0 | 33-21-13 | D02698 | | | 5 | | | | SM00030 | | 9 | | 050-099 |
| 672 | 20 | | PA | 8-0 | 33-21-13 | D02698 | | | 5 | | | | D05112P | | 10 | | 150-199 |
| 672 | 20 | | PA | 30-0 | 33-21-13 | D02698 | | | 5 | | | | D05112P | | 10 | | 275-278 |
| 672 | 20 | | PA | 31-0 | 33-21-13 | D02698 | | | 5 | | | | D05112P | | 10 | | 280-299 |
| 673 | 20 | | PA | 9-0 | 33-21-13 | D02698 | | | 7 | | | | GD01014 | A.. | E | | 050-099 |
| 673 | 20 | | PA | 12-0 | 33-21-13 | D02698 | | | 7 | | | | GD04866 | A.. | E | | 150-199 |
| 673 | 20 | | PA | 4-0 | 33-21-13 | D02698 | | | 7 | | | | GD04826 | A.. | E | | 275-278 |
| 673 | 20 | | PA | 5-0 | 33-21-13 | D02698 | | | 7 | | | | GD04826 | A.. | E | | 280-299 |
| 674 | 20 | | PA | 9-0 | 33-21-13 | D02698 | | | 8 | | | | GD01544 | S.. | E | | 050-099 |
| 674 | 20 | | PA | 12-0 | 33-21-13 | D02698 | | | 8 | | | | GD04834 | S.. | E | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 37

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| 674 | 20 | | PA | 4-0 | 33-21-13 | D02698 | | 8 | | | | | GD04822 | S.. | E | | 275-278 |
| 674 | 20 | | PA | 5-0 | 33-21-13 | D02698 | | 8 | | | | | GD04822 | S.. | E | | 280-299 |
| 675 | 20 | | PA | 15-0 | 33-21-13 | D02698 | | 9 | | | | | SP01322 | | 9 | | 050-099 |
| 675 | 20 | | PA | 14-0 | 33-21-13 | D02698 | | 9 | | | | | SP01322 | | 9 | | 150-199, 275-278 |
| 675 | 20 | | PA | 5-0 | 33-21-13 | D02698 | | 9 | | | | | SP01322 | | 9 | | 280-299 |
| 676 | 20 | | PA | 15-0 | 33-21-13 | D02698 | | 10 | | | | | SP01324 | | 9 | | 050-099 |
| 676 | 20 | | PA | 5-0 | 33-21-13 | D02698 | | 10 | | | | | SP01324 | | 9 | | 150-199, 275-299 |
| 677 | 20 | | PA | 12-0 | 33-21-13 | D02698 | | 11 | | | | | SP01326 | | 9 | | 050-099 |
| 677 | 20 | | PA | 14-0 | 33-21-13 | D02698 | | 11 | | | | | SP01326 | | 9 | | 150-199 |
| 677 | 20 | | PA | 13-0 | 33-21-13 | D02698 | | 11 | | | | | SP01326 | | 9 | | 275-299 |
| 678 | 20 | | PA | 12-0 | 33-21-13 | D02698 | | 12 | | | | | SP01328 | | 9 | | 050-099 |
| 678 | 20 | | PA | 14-0 | 33-21-13 | D02698 | | 12 | | | | | SP01328 | | 9 | | 150-199 |
| 678 | 20 | | PA | 13-0 | 33-21-13 | D02698 | | 12 | | | | | SP01328 | | 9 | | 275-299 |
| 679 | 20 | | PA | 7-0 | 33-21-13 | L00250 | | =G | E | | | | GD01544 | S.. | E | | 050-099 |
| 679 | 20 | | PA | 18-0 | 33-21-13 | L00250 | | =G | E | | | | GD04914 | S.. | E | | 150-199 |
| 679 | 20 | | PA | 6-0 | 33-21-13 | L00250 | | =G | E | | | | GD01544 | S.. | E | | 275-299 |
| 680 | 20 | | PA | 7-0 | 33-21-13 | L00251 | | =G | E | | | | GD01614 | S.. | E | | 050-099 |
| 680 | 20 | | PA | 59-0 | 33-21-13 | L00251 | | =G | E | | | | GD04892 | S.. | E | | 150-199 |
| 680 | 20 | | PA | 5-0 | 33-21-13 | L00251 | | =G | E | | | | GD04828 | S.. | E | | 275-278 |
| 680 | 20 | | PA | 4-0 | 33-21-13 | L00251 | | =G | E | | | | GD04828 | S.. | E | | 280-299 |
| 681 | 20 | | PA | 29-0 | 33-21-13 | SP01326 | | | 9 | | | | SP01334 | | 9 | | 050-099 |
| 681 | 20 | | PA | 28-0 | 33-21-13 | SP01326 | | | 9 | | | | SP01334 | | 9 | | 150-199 |
| 681 | 20 | | PA | 31-0 | 33-21-13 | SP01326 | | | 9 | | | | SP01334 | | 9 | | 275-278 |
| 681 | 20 | | PA | 30-0 | 33-21-13 | SP01326 | | | 9 | | | | SP01334 | | 9 | | 280-299 |
| 682 | 20 | | PA | 29-0 | 33-21-13 | SP01328 | | | 9 | | | | SP01336 | | 9 | | 050-099 |
| 682 | 20 | | PA | 28-0 | 33-21-13 | SP01328 | | | 9 | | | | SP01336 | | 9 | | 150-199 |
| 682 | 20 | | PA | 31-0 | 33-21-13 | SP01328 | | | 9 | | | | SP01336 | | 9 | | 275-278 |
| 682 | 20 | | PA | 32-0 | 33-21-13 | SP01328 | | | 9 | | | | SP01336 | | 9 | | 280-299 |
| 683 | 20 | | PA | 23-0 | 33-21-13 | D02700 | | | 2 | | | | SP01346 | | 9 | | 050-099 |
| 683 | 20 | | PA | 27-0 | 33-21-13 | D02700 | | | 2 | | | | SP01346 | | 9 | | 150-199 |
| 683 | 20 | | PA | 26-0 | 33-21-13 | D02700 | | | 2 | | | | SP01346 | | 9 | | 275-278 |
| 683 | 20 | | PA | 24-0 | 33-21-13 | D02700 | | | 2 | | | | SP01346 | | 9 | | 280-299 |
| 684 | 20 | | PA | 23-0 | 33-21-13 | D02700 | | | 3 | | | | SP01348 | | 9 | | 050-099 |
| 684 | 20 | | PA | 27-0 | 33-21-13 | D02700 | | | 3 | | | | SP01348 | | 9 | | 150-199 |
| 684 | 20 | | PA | 26-0 | 33-21-13 | D02700 | | | 3 | | | | SP01348 | | 9 | | 275-278 |
| 684 | 20 | | PA | 24-0 | 33-21-13 | D02700 | | | 3 | | | | SP01348 | | 9 | | 280-299 |
| 685 | 20 | | PA | 15-0 | 33-21-13 | D02700 | | | 5 | | | | SM00031 | | 9 | | 050-099 |
| 685 | 20 | | PA | 8-0 | 33-21-13 | D02700 | | | 5 | | | | SM00031 | | 9 | | 150-199 |
| 685 | 20 | | PA | 6-0 | 33-21-13 | D02700 | | | 5 | | | | SM00031 | | 9 | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 38
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| 686 | 20 | | PA | 10-0 | 33-21-13 | D02700 | | 7 | | | | | GD01550 | A.. | E | | 050-099 |
| 686 | 20 | | PA | 11-0 | 33-21-13 | D02700 | | 7 | | | | | GD04628 | A.. | E | | 150-199 |
| 686 | 20 | | PA | 12-0 | 33-21-13 | D02700 | | 7 | | | | | GD00685 | A.. | E | | 275-278 |
| 686 | 20 | | PA | 9-0 | 33-21-13 | D02700 | | 7 | | | | | GD00685 | A.. | E | | 280-299 |
| 687 | 20 | | PA | 8-0 | 33-21-13 | D02700 | | 8 | | | | | GD02902 | S.. | E | | 050-099 |
| 687 | 20 | | PA | 12-0 | 33-21-13 | D02700 | | 8 | | | | | GD04630 | S.. | E | | 150-199 |
| 687 | 20 | | PA | 12-0 | 33-21-13 | D02700 | | 8 | | | | | GD00681 | S.. | E | | 275-278 |
| 687 | 20 | | PA | 9-0 | 33-21-13 | D02700 | | 8 | | | | | GD00681 | S.. | E | | 280-299 |
| 688 | 20 | | PA | 16-0 | 33-21-13 | D02700 | | 9 | | | | | SP01338 | | 9 | | 050-099, 150-199 |
| 688 | 20 | | PA | 13-0 | 33-21-13 | D02700 | | 9 | | | | | SP01338 | | 9 | | 275-278 |
| 688 | 20 | | PA | 14-0 | 33-21-13 | D02700 | | 9 | | | | | SP01338 | | 9 | | 280-299 |
| 689 | 20 | | PA | 16-0 | 33-21-13 | D02700 | | 10 | | | | | SP01340 | | 9 | | 050-099, 150-199 |
| 689 | 20 | | PA | 13-0 | 33-21-13 | D02700 | | 10 | | | | | SP01340 | | 9 | | 275-278 |
| 689 | 20 | | PA | 14-0 | 33-21-13 | D02700 | | 10 | | | | | SP01340 | | 9 | | 280-299 |
| 690 | 20 | | PA | 11-0 | 33-21-13 | D02700 | | 11 | | | | | SP01342 | | 9 | | 050-099, 150-199, 275-278 |
| 690 | 20 | | PA | 12-0 | 33-21-13 | D02700 | | 11 | | | | | SP01342 | | 9 | | 280-299 |
| 691 | 20 | | PA | 11-0 | 33-21-13 | D02700 | | 12 | | | | | SP01344 | | 9 | | 050-099, 150-199, 275-278 |
| 691 | 20 | | PA | 12-0 | 33-21-13 | D02700 | | 12 | | | | | SP01344 | | 9 | | 280-299 |
| 692 | 20 | | PA | 7-0 | 33-21-13 | L00252 | =G | E | | | | | GD02902 | S.. | E | | 050-099 |
| 692 | 20 | | PA | 15-0 | 33-21-13 | L00252 | =G | E | | | | | GD00681 | S.. | E | | 150-199 |
| 692 | 20 | | PA | 12-0 | 33-21-13 | L00252 | =G | E | | | | | GD00681 | S.. | E | | 275-299 |
| 693 | 20 | | PA | 8-0 | 33-21-13 | L00253 | =G | E | | | | | GD01458 | S.. | E | | 050-099 |
| 693 | 20 | | PA | 6-0 | 33-21-13 | L00253 | =G | E | | | | | GD05306 | S.. | E | | 150-199 |
| 693 | 20 | | PA | 15-0 | 33-21-13 | L00253 | =G | E | | | | | GD01458 | S.. | E | | 275-299 |
| 694 | 20 | | PA | 33-0 | 33-21-13 | SP01342 | | 9 | | | | | SP01350 | | 9 | | 050-099, 280-299 |
| 694 | 20 | | PA | 28-0 | 33-21-13 | SP01342 | | 9 | | | | | SP01350 | | 9 | | 150-199 |
| 694 | 20 | | PA | 32-0 | 33-21-13 | SP01342 | | 9 | | | | | SP01350 | | 9 | | 275-278 |
| 695 | 20 | | PA | 33-0 | 33-21-13 | SP01344 | | 9 | | | | | SP01352 | | 9 | | 050-099, 280-299 |
| 695 | 20 | | PA | 28-0 | 33-21-13 | SP01344 | | 9 | | | | | SP01352 | | 9 | | 150-199 |
| 695 | 20 | | PA | 32-0 | 33-21-13 | SP01344 | | 9 | | | | | SP01352 | | 9 | | 275-278 |
| 696 | 20 | | PA | 9-0 | 33-21-13 | D05112P | | 2 | | | | | SM00031 | | 9 | | 050-099 |
| 696 | 20 | | PA | 17-0 | 33-21-13 | D05112P | | 2 | | | | | SM00031 | | 9 | | 150-199, 275-299 |
| 697 | 20 | | PA | 20-0 | 33-21-13 | D02734 | | 2 | | | | | SP01362 | | 9 | | 050-099 |
| 697 | 20 | | PA | 31-0 | 33-21-13 | D02734 | | 2 | | | | | SP01362 | | 9 | | 150-199 |
| 697 | 20 | | PA | 30-0 | 33-21-13 | D02734 | | 2 | | | | | SP01362 | | 9 | | 275-299 |
| 698 | 20 | | PA | 20-0 | 33-21-13 | D02734 | | 3 | | | | | SP01364 | | 9 | | 050-099 |
| 698 | 20 | | PA | 31-0 | 33-21-13 | D02734 | | 3 | | | | | SP01364 | | 9 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 39

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | |
| 698 | 20 | | PA | | 30-0 | 33-21-13 | D02734 | | | 3 | | | | | 275-299 |
| 699 | 20 | | PA | | 5-0 | 33-21-13 | D02734 | | | 5 | | | | | 050-099 |
| 699 | 20 | | PA | | 10-0 | 33-21-13 | D02734 | | | 5 | | | | | 150-199, 275-278 |
| 699 | 20 | | PA | | 11-0 | 33-21-13 | D02734 | | | 5 | | | | | 280-299 |
| 700 | 20 | | PA | | 9-0 | 33-21-13 | D02734 | | | 7 | | | A.. | E | 050-099 |
| 700 | 20 | | PA | | 10-0 | 33-21-13 | D02734 | | | 7 | | | A.. | E | 150-199 |
| 700 | 20 | | PA | | 9-0 | 33-21-13 | D02734 | | | 7 | | | A.. | E | 275-299 |
| 701 | 20 | | PA | | 10-0 | 33-21-13 | D02734 | | | 8 | | | S.. | E | 050-099 |
| 701 | 20 | | PA | | 10-0 | 33-21-13 | D02734 | | | 8 | | | S.. | E | 150-199 |
| 701 | 20 | | PA | | 9-0 | 33-21-13 | D02734 | | | 8 | | | S.. | E | 275-299 |
| 702 | 20 | | PA | | 15-0 | 33-21-13 | D02734 | | | 9 | | | | | ALL |
| 703 | 20 | | PA | | 15-0 | 33-21-13 | D02734 | | | 10 | | | | | ALL |
| 704 | 20 | | PA | | 13-0 | 33-21-13 | D02734 | | | 11 | | | | | ALL |
| 705 | 20 | | PA | | 13-0 | 33-21-13 | D02734 | | | 12 | | | | | ALL |
| 706 | 20 | | PA | | 19-0 | 33-21-13 | L00254 | | =G | E | | | S.. | E | 050-099 |
| 706 | 20 | | PA | | 4-0 | 33-21-13 | L00254 | | =G | E | | | S.. | E | 150-199 |
| 706 | 20 | | PA | | 5-0 | 33-21-13 | L00254 | | =G | E | | | S.. | E | 275-299 |
| 707 | 20 | | PA | | 6-0 | 33-21-13 | L00255 | | =G | E | | | S.. | E | 050-099 |
| 707 | 20 | | PA | | 45-0 | 33-21-13 | L00255 | | =G | E | | | S.. | E | 150-199 |
| 707 | 20 | | PA | | 9-0 | 33-21-13 | L00255 | | =G | E | | | S.. | E | 275-299 |
| 708 | 20 | | PA | | 29-0 | 33-21-13 | SP01358 | | | 9 | | | | | 050-099 |
| 708 | 20 | | PA | | 30-0 | 33-21-13 | SP01366 | | | 9 | | | | | 150-199 |
| 708 | 20 | | PA | | 28-0 | 33-21-13 | SP01366 | | | 9 | | | | | 275-278 |
| 708 | 20 | | PA | | 29-0 | 33-21-13 | SP01366 | | | 9 | | | | | 280-299 |
| 709 | 20 | | PA | | 29-0 | 33-21-13 | SP01360 | | | 9 | | | | | 050-099 |
| 709 | 20 | | PA | | 28-0 | 33-21-13 | SP01368 | | | 9 | | | | | 150-199, 275-278 |
| 709 | 20 | | PA | | 29-0 | 33-21-13 | SP01368 | | | 9 | | | | | 280-299 |
| 710 | 20 | | PA | | 25-0 | 33-21-13 | D00426 | | | 2 | | | | | 050-099 |
| 711 | 20 | | PA | | 25-0 | 33-21-13 | D00426 | | | 3 | | | | | 050-099 |
| 712 | 20 | | PA | | 16-0 | 33-21-13 | D00426 | | | 5 | | | | 10 | 050-099 |
| 713 | 20 | | PA | | 8-0 | 33-21-13 | D00426 | | | 7 | | | A.. | E | 050-099 |
| 714 | 20 | | PA | | 8-0 | 33-21-13 | D00426 | | | 8 | | | S.. | E | 050-099 |
| 715 | 20 | | PA | | 10-0 | 33-21-13 | D00426 | | | 9 | | | | | 050-099 |
| 716 | 20 | | PA | | 10-0 | 33-21-13 | D00426 | | | 10 | | | | | 050-099 |
| 717 | 20 | | PA | | 11-0 | 33-21-13 | D00426 | | | 11 | | | | | 050-099 |
| 718 | 20 | | PA | | 11-0 | 33-21-13 | D00426 | | | 12 | | | | | 050-099 |
| 719 | 20 | | PA | | 8-0 | 33-21-13 | L00282 | | =G | E | | | S.. | E | 050-099 |
| 720 | 20 | | PA | | 8-0 | 33-21-13 | L00283 | | =G | E | | | S.. | E | 050-099 |
| 721 | 20 | | PA | | 24-0 | 33-21-13 | SP01374 | | | 9 | | | | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 40
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| 722 | 20 | | PA | 24-0 | 33-21-13 | SP01376 | | 9 | | | | | SP01384 | | 9 | | 050-099 |
| 724 | 20 | | PA | 41-9 | 33-21-11 | L00761 | =G | E | | | | | GD04846 | S.. | E | | 150-199 |
| 724 | 20 | | PA | 8-3 | 33-21-11 | L00761 | =G | E | | | | | GD04846 | S.. | E | | 275-278 |
| 724 | 20 | | PA | 11-0 | 33-21-11 | STA0707R | CAP | Y | | | | | GD04824 | S.. | E | | 280-299 |
| 758 | 20 | | PA | 6-0 | 33-21-11 | L00756 | =G | E | | | | | GD04850 | S.. | E | | 150-199, 275-278 |
| 758 | 20 | | PA | 9-0 | 33-21-11 | STA0654L | CAP | Y | | | | | GD04850 | S.. | E | | 280-299 |
| 760 | 20 | | PA | 30-0 | 33-21-11 | SP02822 | | 9 | | | | | SP02846 | | 9 | | 150-199 |
| 760 | 20 | | PA | 23-0 | 33-21-11 | STA0743L | CAP | Y | | | | | SP05252 | | 9 | | 280-299 |
| 761 | 20 | | PA | 30-0 | 33-21-11 | SP02824 | | 9 | | | | | SP02844 | | 9 | | 150-199 |
| 761 | 20 | | PA | 23-0 | 33-21-11 | STA0743L | CAP | Y | | | | | SP05254 | | 9 | | 280-299 |
| 762 | 20 | | PA | 27-0 | 33-21-11 | SP02828 | | 9 | | | | | SP02842 | | 9 | | 150-199, 275-278 |
| 762 | 20 | | PA | 27-0 | 33-21-11 | STA0654L | CAP | Y | | | | | SP02842 | | 9 | | 280-299 |
| 763 | 20 | | PA | 27-0 | 33-21-11 | SP02830 | | 9 | | | | | SP02840 | | 9 | | 150-199, 275-278 |
| 763 | 20 | | PA | 27-0 | 33-21-11 | STA0654L | CAP | Y | | | | | SP02840 | | 9 | | 280-299 |
| 765 | 20 | | PA | 34-0 | 33-21-11 | SP02834 | | 9 | | | | | SP02902 | | 9 | | 150-199 |
| 765 | 20 | | PA | 24-0 | 33-21-11 | SP02834 | | 9 | | | | | SP02902 | | 9 | | 275-278 |
| 765 | 20 | | PA | 11-0 | 33-21-11 | ST0675L | CAP | Y | | | | | SM00075 | | 9 | | 280-299 |
| 766 | 20 | | PA | 34-0 | 33-21-11 | SP02836 | | 9 | | | | | SP02900 | | 9 | | 150-199 |
| 766 | 20 | | PA | 24-0 | 33-21-11 | SP02836 | | 9 | | | | | SP02900 | | 9 | | 275-278 |
| 766 | 20 | | PA | 11-0 | 33-21-11 | ST0675L | CAP | Y | | | | | SM00074 | | 9 | | 280-299 |
| 767 | 20 | | PA | 35-0 | 33-21-11 | D11164 | | 11 | | | | | SP02900 | | 9 | | 150-199 |
| 767 | 20 | | PA | 23-0 | 33-21-11 | D11164 | | 11 | | | | | SP02900 | | 9 | | 275-278 |
| 767 | 20 | | PA | 2-0 | 33-21-11 | D11164 | | 11 | | | | | SM00074 | | 9 | | 280-299 |
| 768 | 20 | | PA | 35-0 | 33-21-11 | D11164 | | 12 | | | | | SP02902 | | 9 | | 150-199 |
| 768 | 20 | | PA | 23-0 | 33-21-11 | D11164 | | 12 | | | | | SP02902 | | 9 | | 275-278 |
| 768 | 20 | | PA | 2-0 | 33-21-11 | D11164 | | 12 | | | | | SM00075 | | 9 | | 280-299 |
| 769 | 20 | | PA | 4-0 | 33-21-11 | D11164 | | 7 | | | | | GD04826 | A.. | E | | 150-199 |
| 769 | 20 | | PA | 4-0 | 33-21-11 | D11164 | | 7 | | | | | GD04842 | A.. | E | | 275-278 |
| 769 | 20 | | PA | 5-0 | 33-21-11 | D11164 | | 7 | | | | | GD04842 | A.. | E | | 280-299 |
| 770 | 20 | | PA | 4-0 | 33-21-11 | D11164 | | 8 | | | | | GD04822 | S.. | E | | 150-199 |
| 770 | 20 | | PA | 4-0 | 33-21-11 | D11164 | | 8 | | | | | GD04844 | S.. | E | | 275-299 |
| 772 | 24 | | PK | 69-0 | 33-21-12 | D05110P | | 20 | | | | | D05112P | | 12 | | 275-278 |
| 772 | 24 | | PK | 70-0 | 33-21-12 | D05110P | | 20 | | | | | D05112P | | 12 | | 280-299 |
| 773 | 20 | | PA | 29-0 | 33-21-11 | D11168 | | 11 | | | | | SP02844 | | 9 | | 150-199 |
| 773 | 20 | | PA | 19-0 | 33-21-11 | D11168 | | 11 | | | | | SP05254 | | 9 | | 280-299 |
| 774 | 20 | | PA | 29-0 | 33-21-11 | D11168 | | 12 | | | | | SP02846 | | 9 | | 150-199 |
| 774 | 20 | | PA | 19-0 | 33-21-11 | D11168 | | 12 | | | | | SP05252 | | 9 | | 280-299 |
| 775 | 20 | | PA | 3-0 | 33-21-11 | D11168 | | 7 | | | | | GD04826 | A.. | E | | 150-199 |
| 775 | 20 | | PA | 10-0 | 33-21-11 | D11168 | | 7 | | | | | GD04818 | A.. | E | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 41

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|-----|---|--|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | | | |
| 776 | 20 | | PA | | 3-0 | 33-21-11 | D11168 | | | | 8 | | | | GD04822 | S.. | E | | 150-199 |
| 776 | 20 | | PA | | 23-0 | 33-21-11 | D11168 | | | | 8 | | | | GD04820 | S.. | E | | 280-299 |
| 778 | 24 | | PK | | 69-0 | 33-21-12 | D05110P | | | | 19 | | | | D05112P | 11 | | | 275-278 |
| 778 | 24 | | PK | | 70-0 | 33-21-12 | D05110P | | | | 19 | | | | D05112P | 11 | | | 280-299 |
| 786 | 20 | | PA | | 32-0 | 33-21-32 | D05110P | | | | 21 | | | | D11172 | 5 | | | 150-154, 157-165, 167-199, 275-299 |
| 786 | 20 | | PQ | O6 | 32-0 | 33-21-32 | D05110P | | | | 21 | | | | D11172 | 5 | | | 155-156, 166 |
| 786Z | | | | O6 | 0-0 | 33-21-32 | D05110P | | | | DED | | | | D11172 | DED | | | 155-156, 166 |
| 787 | 20 | | PA | | 4-0 | 33-21-32 | D11172 | | | | 7 | | | | GD04868 | A.. | E | | 150-154, 157-165, 167-199, 275-299 |
| 787 | 20 | | PQ | O7 | 4-0 | 33-21-32 | D11172 | | | | 7 | | | | GD04868 | A.. | E | | 155-156, 166 |
| 787Z | | | | O7 | 0-0 | 33-21-32 | D11172 | | | | DED | | | | GD04868 | DED | | | 155-156, 166 |
| 788 | 20 | | PA | | 4-0 | 33-21-32 | D11172 | | | | 8 | | | | GD04850 | S.. | E | | 150-199, 275-299 |
| 789 | 22 | | PA | | 11-0 | 33-21-32 | D11172 | | | | 2 | | | | D11174 | 1 | | | 150-199, 275-299 |
| 790 | 22 | | PA | | 11-0 | 33-21-32 | D11172 | | | | 3 | | | | D11174 | 2 | | | 150-199, 275-299 |
| 791 | 22 | | PA | | 6-0 | 33-21-32 | SM00048 | | | | 9 | | | | D11172 | 11 | | | 150-199, 275-299 |
| 792 | 22 | | PA | | 6-0 | 33-21-32 | SM00049 | | | | 9 | | | | D11172 | 12 | | | 150-199, 275-299 |
| 793 | 22 | | PA | | 25-0 | 33-21-32 | D11172 | | | | 9 | | | | D11176 | 1 | | | 150-199, 275-278 |
| 793 | 22 | | PA | | 26-0 | 33-21-32 | D11172 | | | | 9 | | | | D11176 | 1 | | | 280-299 |
| 794 | 22 | | PA | | 25-0 | 33-21-32 | D11172 | | | | 10 | | | | D11176 | 2 | | | 150-199, 275-278 |
| 794 | 22 | | PA | | 26-0 | 33-21-32 | D11172 | | | | 10 | | | | D11176 | 2 | | | 280-299 |
| 795 | 22 | | PA | | 8-0 | 33-21-32 | SM00048 | | | | 9 | | | | D11174 | 3 | | | 150-199, 275-299 |
| 796 | 22 | | PA | | 8-0 | 33-21-32 | SM00049 | | | | 9 | | | | D11174 | 4 | | | 150-199, 275-299 |
| 797 | 20 | | PA | | 4-0 | 33-21-32 | D11174 | | | | 5 | | | | GD04870 | S.. | E | | 150-199, 275-299 |
| 798 | 22 | | PA | | 20-0 | 33-21-32 | SM00048 | | | | 9 | | | | D11176 | 3 | | | 150-199, 275-278 |
| 798 | 22 | | PA | | 23-0 | 33-21-32 | SM00048 | | | | 9 | | | | D11176 | 3 | | | 280-299 |
| 799 | 20 | | PA | | 59-0 | 33-26-11 | D05110P | | | | 41 | | | | D05112P | 9 | | | 050-099 |
| 799 | 22 | | PA | | 20-0 | 33-21-32 | SM00049 | | | | 9 | | | | D11176 | 4 | | | 150-199, 275-278 |
| 799 | 22 | | PA | | 23-0 | 33-21-32 | SM00049 | | | | 9 | | | | D11176 | 4 | | | 280-299 |
| 800 | 20 | | PA | | 5-0 | 33-21-32 | D11176 | | | | 5 | | | | GD04872 | S.. | E | | 150-199, 275-278 |
| 800 | 20 | | PA | | 4-0 | 33-21-32 | D11176 | | | | 5 | | | | GD04872 | S.. | E | | 280-299 |
| 801 | 22 | | PA | | 14-0 | 33-21-34 | D02942 | | | | 9 | | | | D11178 | 1 | | | 150-199 |
| 801 | 22 | | PA | | 18-0 | 33-21-34 | D02942 | | | | 9 | | | | D11178 | 1 | | | 275-278 |
| 801 | 22 | | PA | | 17-0 | 33-21-34 | D02942 | | | | 9 | | | | D11178 | 1 | | | 280-299 |
| 802 | 22 | | PA | | 14-0 | 33-21-34 | D02942 | | | | 10 | | | | D11178 | 2 | | | 150-199 |
| 802 | 22 | | PA | | 18-0 | 33-21-34 | D02942 | | | | 10 | | | | D11178 | 2 | | | 275-278 |
| 802 | 22 | | PA | | 17-0 | 33-21-34 | D02942 | | | | 10 | | | | D11178 | 2 | | | 280-299 |
| 803 | 20 | | PA | | 4-0 | 33-21-34 | GD04626 | | | | S.. | E | | | D11178 | 5 | | | 150-199, 275-278 |
| 803 | 20 | | PA | | 5-0 | 33-21-34 | GD04626 | | | | S.. | E | | | D11178 | 5 | | | 280-299 |

WIRE LIST

D280T132

91-21-11
Section W0810
Page 42
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | |
| 804 | 22 | | PA | | 16-0 | 33-21-34 | SM00007 | | | 9 | | | D11178 | 4 | | 150-199, 275-299 |
| 805 | 22 | | PA | | 16-0 | 33-21-34 | SM00006 | | | 9 | | | D11178 | 3 | | 150-199, 275-299 |
| 806 | 20 | | PA | | 72-0 | 33-21-34 | D05110P | | | 26 | | | D05112P | 21 | | 150-154, 157-165, 167-199 |
| 806 | 20 | PQ | Q6 | | 72-0 | 33-21-34 | D05110P | | | 26 | | | D05112P | 21 | | 155-156, 166 |
| 806 | 20 | PA | | | 69-0 | 33-21-34 | D05110P | | | 26 | | | D05112P | 21 | | 275-278 |
| 806 | 20 | PA | | | 70-0 | 33-21-34 | D05110P | | | 26 | | | D05112P | 21 | | 280-299 |
| 806Z | | | Q6 | | 0-0 | 33-21-34 | D05110P | | DED | | | | D05112P | DED | | 155-156, 166 |
| 807 | 20 | PA | | | 29-0 | 33-21-11 | D05110P | | | 18 | | | SM00030 | 9 | | 050-099 |
| 812 | 20 | PA | | | 6-0 | 33-21-11 | D08688J | | | 1 | | | GD06735 | A.. | 2 | 050-099 |
| 814 | 20 | PA | | | 58-0 | 33-21-31 | D05110P | | | 11 | | | D05112P | 17 | | 050-099 |
| 814 | 20 | PA | | | 72-0 | SPARE | D05110P | | | 11 | | | D05112P | 17 | | 150-157 |
| 814 | 20 | PA | | | 72-0 | 33-21-31 | D05110P | | | 11 | | | D05112P | 17 | | 162-199 |
| 814 | 20 | PA | | | 69-0 | SPARE | D05110P | | | 11 | | | D05112P | 17 | | 275-278 |
| 814 | 20 | PA | | | 70-0 | SPARE | D05110P | | | 11 | | | D05112P | 17 | | 280-299 |
| 821 | 22 | PA | | | 19-0 | 33-21-32 | D02946 | | | 2 | | | D03182 | 1 | | 275-278 |
| 821 | 22 | PA | | | 21-0 | 33-21-32 | D02946 | | | 2 | | | D03182 | 1 | | 280-299 |
| 822 | 22 | PA | | | 19-0 | 33-21-32 | D02946 | | | 3 | | | D03182 | 2 | | 275-278 |
| 822 | 22 | PA | | | 21-0 | 33-21-32 | D02946 | | | 3 | | | D03182 | 2 | | 280-299 |
| 823 | 22 | PA | | | 17-0 | 33-21-32 | SM00011 | | | 9 | | | D03182 | 3 | | 275-299 |
| 824 | 22 | PA | | | 17-0 | 33-21-32 | SM00012 | | | 9 | | | D03182 | 4 | | 275-299 |
| 825 | 20 | PA | | | 3-0 | 33-21-32 | GD02038 | | S.. | E | | | D03182 | 5 | | 275-278 |
| 825 | 20 | PA | | | 4-0 | 33-21-32 | GD02038 | | S.. | E | | | D03182 | 5 | | 280-299 |
| 851 | 16 | PA | | | 72-0 | 33-21-34 | D05110P | | | 40 | | | D05112P | 23 | | 150-154, 157-199 |
| 851 | 16 | PQ | V1 | | 72-0 | 33-21-34 | D05110P | | | 40 | | | D05112P | 23 | | 155-156 |
| 851Z | | | V1 | | 0-0 | 33-21-34 | D05110P | | DED | | | | D05112P | DED | | 155-156 |
| 871 | 20 | PA | | | 5-0 | 33-21-11 | D08688J | | | 1 | | | GD06735 | A.. | 2 | 150-199 |
| 872 | 24 | PK | | | 14-0 | 33-21-11 | D08688J | | | 2 | | | D05110P | 46 | | 050-099 |
| 872 | 24 | PK | | | 13-0 | 33-21-11 | D08688J | | | 2 | | | D05110P | 46 | | 150-199 |
| 873 | 24 | PK | | | 14-0 | 33-21-11 | D08688J | | | 3 | | | D05110P | 47 | | 050-099 |
| 873 | 24 | PK | | | 13-0 | 33-21-11 | D08688J | | | 3 | | | D05110P | 47 | | 150-199 |
| 874 | 20 | PA | | | 6-0 | 33-21-11 | D08688J | | | 4 | | | GD06735 | A.. | 2 | 050-099 |
| 874 | 20 | PA | | | 5-0 | 33-21-11 | D08688J | | | 4 | | | GD06735 | A.. | 2 | 150-199 |
| 875 | 24 | PK | | | 14-0 | 33-21-11 | D08688J | | | 5 | | | D05110P | 49 | | 050-099 |
| 875 | 24 | PK | | | 13-0 | 33-21-11 | D08688J | | | 5 | | | D05110P | 49 | | 150-199 |
| 876 | 24 | PK | | | 14-0 | 33-21-11 | D08688J | | | 6 | | | D05110P | 48 | | 050-099 |
| 876 | 24 | PK | | | 13-0 | 33-21-11 | D08688J | | | 6 | | | D05110P | 48 | | 150-199 |
| 877 | 20 | PA | | | 6-0 | 33-21-11 | D08688J | | | 7 | | | GD06735 | D.. | 2 | 050-099 |
| 877 | 20 | PA | | | 5-0 | 33-21-11 | D08688J | | | 7 | | | GD06735 | D.. | 2 | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 43

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | |
| 878 | 24 | | PK | 14-0 | 33-21-11 | D08688J | | 8 | | | D05110P | | 50 | | | 050-099 |
| 878 | 24 | | PK | 13-0 | 33-21-11 | D08688J | | 8 | | | D05110P | | 50 | | | 150-199 |
| 879 | 24 | | PK | 64-0 | 33-21-12 | D06736P | | 1 | | | D08688J | | 9 | | | 050-099 |
| 879 | 20 | | PA | 74-0 | 33-21-12 | D08688J | | 9 | | | D06736P | | 1 | | | 150-199 |
| 880 | 24 | | PK | 14-0 | 33-21-12 | D05110P | | 44 | | | D08688J | | 10 | | | 050-099 |
| 880 | 24 | | PK | 13-0 | 33-21-12 | D08688J | | 10 | | | D05110P | | 44 | | | 150-199 |
| 881 | 24 | | PK | 64-0 | 33-21-12 | D06736P | | 3 | | | D08688J | | 11 | | | 050-099 |
| 881 | 20 | | PA | 74-0 | 33-21-12 | D08688J | | 11 | | | D06736P | | 3 | | | 150-199 |
| 882 | 24 | | PK | 14-0 | 33-21-12 | D05110P | | 45 | | | D08688J | | 12 | | | 050-099 |
| 882 | 24 | | PK | 13-0 | 33-21-12 | D08688J | | 12 | | | D05110P | | 45 | | | 150-199 |
| 883 | 24 | | PK | 64-0 | 33-21-12 | D06736P | | 5 | | | D08688J | | 13 | | | 050-099 |
| 883 | 20 | | PA | 74-0 | 33-21-12 | D08688J | | 13 | | | D06736P | | 5 | | | 150-199 |
| 884 | 24 | | PK | 64-0 | 33-21-12 | D06736P | | 6 | | | D08688J | | 14 | | | 050-099 |
| 884 | 20 | | PA | 74-0 | 33-21-12 | D08688J | | 14 | | | D06736P | | 6 | | | 150-199 |
| 885 | 24 | | PK | 64-0 | 33-21-12 | D06736P | | 7 | | | D08688J | | 15 | | | 050-099 |
| 885 | 20 | | PA | 74-0 | 33-21-12 | D08688J | | 15 | | | D06736P | | 7 | | | 150-199 |
| 886 | 24 | | PK | 64-0 | 33-21-12 | D06736P | | 8 | | | D08688J | | 16 | | | 050-099 |
| 886 | 20 | | PA | 74-0 | 33-21-12 | D08688J | | 16 | | | D06736P | | 8 | | | 150-199 |
| 887 | 24 | | PK | 59-0 | 33-21-12 | D05110P | | 55 | | | D06736P | | 2 | | | 050-099 |
| 887 | 20 | | PA | 69-0 | 33-21-12 | D05110P | | 55 | | | D06736P | | 2 | | | 150-199 |
| 888 | 22 | | PA | 14-0 | 33-22-41 | D05110P | | 51 | | | D08688J | | 17 | | | 050-099 |
| 888 | 24 | | PK | 13-0 | 33-22-41 | D08688J | | 17 | | | D05110P | | 51 | | | 150-199 |
| 889 | 22 | | PA | 14-0 | 33-22-41 | D05110P | | 52 | | | D08688J | | 18 | | | 050-099 |
| 889 | 24 | | PK | 13-0 | 33-22-41 | D08688J | | 18 | | | D05110P | | 52 | | | 150-199 |
| 890 | 22 | | PA | 14-0 | 33-22-41 | D05110P | | 53 | | | D08688J | | 19 | | | 050-099 |
| 890 | 24 | | PK | 13-0 | 33-22-41 | D08688J | | 19 | | | D05110P | | 53 | | | 150-199 |
| 891 | 22 | | PA | 14-0 | 33-22-41 | D05110P | | 54 | | | D08688J | | 20 | | | 050-099 |
| 891 | 24 | | PK | 13-0 | 33-22-41 | D08688J | | 20 | | | D05110P | | 54 | | | 150-199 |
| 894 | 20 | | PA | 59-0 | 33-26-11 | D05110P | | 42 | | | D05112P | | 6 | | | 050-099 |
| 894 | 20 | | PA | 37-0 | 33-26-11 | D05112P | | 3 | | | SP03634 | | | 9 | | 150-199 |
| 895 | 24 | | PK | 59-0 | 33-21-12 | D05808P | | 6 | | | D06736P | | 13 | | | 050-099 |
| 895 | 24 | | PK | 69-0 | 33-21-12 | D05808P | | 6 | | | D06736P | | 13 | | | 150-199 |
| 896 | 20 | | PA | 64-0 | 33-22-42 | D06736P | | 9 | | | D08688J | | 22 | | | 050-099 |
| 896 | 20 | | PA | 74-0 | 33-22-42 | D08688J | | 22 | | | D06736P | | 9 | | | 150-199 |
| 897 | 20 | | PA | 64-0 | 33-22-42 | D06736P | | 10 | | | D08688J | | 24 | | | 050-099 |
| 897 | 20 | | PA | 74-0 | 33-22-42 | D06736P | | 10 | | | D08688J | | 24 | | | 150-199 |
| 898 | 24 | | PK | 59-0 | 33-21-12 | D05808P | | 7 | | | D06736P | | 11 | | | 050-099 |
| 898 | 20 | | PA | 69-0 | 33-21-12 | D05808P | | 7 | | | D06736P | | 11 | | | 150-199 |
| 899 | 24 | | PK | 59-0 | 33-21-12 | D05808P | | 8 | | | D06736P | | 12 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 44

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| 899 | 20 | | PA | 69-0 | 33-21-12 | D05808P | | 8 | | | | | D06736P | 12 | | | 150-199 |
| 904 | 20 | | PA | 9-0 | 33-26-21 | D08688J | | 30 | | | | | SP03672 | | 9 | | 150-199 |
| 905 | 20 | | PA | 9-0 | 33-26-21 | D08688J | | 31 | | | | | SP03674 | | 9 | | 150-199 |
| 906 | 20 | | PA | 70-0 | 33-26-21 | D08688J | | 32 | | | | | SP03720 | | 9 | | 150-199 |
| 908 | 20 | | PA | 70-0 | 33-26-21 | D08688J | | 33 | | | | | SP03722 | | 9 | | 150-199 |
| 910 | 20 | | PA | 69-0 | 33-21-12 | D05110P | | 56 | | | | | D06736P | | 4 | | 150-199 |
| 911 | 20 | | PA | 13-0 | 33-21-12 | D08688J | | 21 | | | | | D05110P | | 1 | | 150-199 |
| A-A | | | | 0-0 | 33-21-11 | L00237 | | | BLK | | | | SP00886 | | 9 | | 275-299 |
| A-B | | | | 0-0 | 33-21-11 | L00237 | | | BLK | | | | SP00888 | | 9 | | 275-299 |
| A-C | | | | 0-0 | 33-21-11 | L00237 | | | WHT | | | | SP00858 | | 9 | | 275-299 |
| A-D | | | | 0-0 | 33-21-11 | L00237 | | | WHT | | | | SP00860 | | 9 | | 275-299 |
| A-E | | | | 0-0 | 33-21-11 | L00760 | | | BLK | | | | SP02800 | | 9 | | 150-199, 275-278 |
| A-F | | | | 0-0 | 33-21-11 | L00760 | | | BLK | | | | SP02802 | | 9 | | 150-199, 275-278 |
| A-G | | | | 0-0 | 33-21-11 | L00760 | | | WHT | | | | SP02834 | | 9 | | 150-199, 275-278 |
| A-H | | | | 0-0 | 33-21-11 | L00760 | | | WHT | | | | SP02836 | | 9 | | 150-199, 275-278 |
| A-K | | | | 0-0 | 33-21-11 | L00761 | | | BLK | | | | SP02804 | | 9 | | 150-199, 275-278 |
| A-L | | | | 0-0 | 33-21-11 | L00761 | | | BLK | | | | SP02806 | | 9 | | 150-199, 275-278 |
| A-M | | | | 0-0 | 33-21-11 | L00761 | | | WHT | | | | SP02902 | | 9 | | 150-199, 275-278 |
| A-N | | | | 0-0 | 33-21-11 | L00761 | | | WHT | | | | SP02900 | | 9 | | 150-199, 275-278 |
| A-R | | | | 0-0 | 33-21-11 | L00757 | | | BLK | | | | SP02810 | | 9 | | 150-199, 275-278 |
| A-S | | | | 0-0 | 33-21-11 | L00757 | | | BLK | | | | SP02812 | | 9 | | 150-199, 275-278 |
| A-T | | | | 0-0 | 33-21-11 | L00757 | | | WHT | | | | SP02840 | | 9 | | 150-199, 275-278 |
| A-U | | | | 0-0 | 33-21-11 | L00757 | | | WHT | | | | SP02842 | | 9 | | 150-199, 275-278 |
| A-W | | | | 0-0 | 33-21-11 | L00765 | | | BLK | | | | SP02818 | | 9 | | 150-199 |
| A-X | | | | 0-0 | 33-21-11 | L00765 | | | BLK | | | | SP02820 | | 9 | | 150-199 |
| A-Y | | | | 0-0 | 33-21-11 | L00765 | | | WHT | | | | SP02846 | | 9 | | 150-199 |
| A-Z | | | | 0-0 | 33-21-11 | L00765 | | | WHT | | | | SP02844 | | 9 | | 150-199 |
| B-A | | | | 0-0 | 33-21-11 | L00236 | | | BLK | | | | SP00862 | | 9 | | 275-299 |
| B-B | | | | 0-0 | 33-21-11 | L00236 | | | BLK | | | | SP00864 | | 9 | | 275-299 |
| B-C | | | | 0-0 | 33-21-11 | L00236 | | | WHT | | | | SP00866 | | 9 | | 275-299 |
| B-D | | | | 0-0 | 33-21-11 | L00236 | | | WHT | | | | SP00868 | | 9 | | 275-299 |
| B-E | | | | 0-0 | 33-21-11 | L00764 | | | BLK | | | | SP02814 | | 9 | | 150-199 |
| B-F | | | | 0-0 | 33-21-11 | L00764 | | | BLK | | | | SP02816 | | 9 | | 150-199 |
| B-G | | | | 0-0 | 33-21-11 | L00764 | | | WHT | | | | SP02822 | | 9 | | 150-199 |
| B-H | | | | 0-0 | 33-21-11 | L00764 | | | WHT | | | | SP02824 | | 9 | | 150-199 |
| B-J | | | | 0-0 | 33-21-11 | L00756 | | | BLK | | | | SP02796 | | 9 | | 150-199, 275-278 |
| B-K | | | | 0-0 | 33-21-11 | L00756 | | | BLK | | | | SP02798 | | 9 | | 150-199, 275-278 |
| B-L | | | | 0-0 | 33-21-11 | L00756 | | | WHT | | | | SP02828 | | 9 | | 150-199, 275-278 |
| B-M | | | | 0-0 | 33-21-11 | L00756 | | | WHT | | | | SP02830 | | 9 | | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 45

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|--|--|--|----------|----------|--------|----|-----|-------|---------|-------|---------|------|--------|-------|------------------|
| | | | | | Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| C-A | | | | | 0-0 | 33-21-11 | L00239 | | BLK | | | | SP00874 | | 9 | | ALL |
| C-B | | | | | 0-0 | 33-21-11 | L00239 | | BLK | | | | SP00876 | | 9 | | ALL |
| C-C | | | | | 0-0 | 33-21-11 | L00239 | | WHT | | | | SP00870 | | 9 | | ALL |
| C-D | | | | | 0-0 | 33-21-11 | L00239 | | WHT | | | | SP00872 | | 9 | | ALL |
| D-A | | | | | 0-0 | 33-21-11 | L00238 | | BLK | | | | SP00878 | | 9 | | ALL |
| D-B | | | | | 0-0 | 33-21-11 | L00238 | | BLK | | | | SP00880 | | 9 | | ALL |
| D-C | | | | | 0-0 | 33-21-11 | L00238 | | WHT | | | | SP00882 | | 9 | | ALL |
| D-D | | | | | 0-0 | 33-21-11 | L00238 | | WHT | | | | SP00884 | | 9 | | ALL |
| E-A | | | | | 0-0 | 33-21-11 | L00244 | | BLK | | | | SP00796 | | 9 | | ALL |
| E-B | | | | | 0-0 | 33-21-11 | L00244 | | BLK | | | | SP00798 | | 9 | | ALL |
| E-C | | | | | 0-0 | 33-21-11 | L00244 | | WHT | | | | SP00800 | | 9 | | ALL |
| E-D | | | | | 0-0 | 33-21-11 | L00244 | | WHT | | | | SP00802 | | 9 | | ALL |
| F-A | | | | | 0-0 | 33-21-11 | L00246 | | BLK | | | | SP00792 | | 9 | | ALL |
| F-B | | | | | 0-0 | 33-21-11 | L00246 | | BLK | | | | SP00794 | | 9 | | ALL |
| F-C | | | | | 0-0 | 33-21-11 | L00246 | | WHT | | | | SP00788 | | 9 | | ALL |
| F-D | | | | | 0-0 | 33-21-11 | L00246 | | WHT | | | | SP00790 | | 9 | | ALL |
| G-A | | | | | 0-0 | 33-21-11 | L00245 | | BLK | | | | SP00812 | | 9 | | 050-099 |
| G-A | | | | | 0-0 | 33-21-13 | L00245 | | BLK | | | | SP00812 | | 9 | | 150-199, 275-278 |
| G-B | | | | | 0-0 | 33-21-11 | L00245 | | BLK | | | | SP00814 | | 9 | | 050-099 |
| G-B | | | | | 0-0 | 33-21-13 | L00245 | | BLK | | | | SP00814 | | 9 | | 150-199, 275-278 |
| G-C | | | | | 0-0 | 33-21-11 | L00245 | | WHT | | | | SP00816 | | 9 | | 050-099 |
| G-C | | | | | 0-0 | 33-21-13 | L00245 | | WHT | | | | SP00816 | | 9 | | 150-199, 275-278 |
| G-D | | | | | 0-0 | 33-21-11 | L00245 | | WHT | | | | SP00818 | | 9 | | 050-099 |
| G-D | | | | | 0-0 | 33-21-13 | L00245 | | WHT | | | | SP00818 | | 9 | | 150-199, 275-278 |
| H-A | | | | | 0-0 | 33-21-13 | L00250 | | BLK | | | | SP01322 | | 9 | | ALL |
| H-B | | | | | 0-0 | 33-21-13 | L00250 | | BLK | | | | SP01324 | | 9 | | ALL |
| H-C | | | | | 0-0 | 33-21-13 | L00250 | | WHT | | | | SP01326 | | 9 | | ALL |
| H-D | | | | | 0-0 | 33-21-13 | L00250 | | WHT | | | | SP01328 | | 9 | | ALL |
| J-A | | | | | 0-0 | 33-21-13 | L00251 | | BLK | | | | SP01330 | | 9 | | ALL |
| J-B | | | | | 0-0 | 33-21-13 | L00251 | | BLK | | | | SP01332 | | 9 | | ALL |
| J-C | | | | | 0-0 | 33-21-13 | L00251 | | WHT | | | | SP01334 | | 9 | | ALL |
| J-D | | | | | 0-0 | 33-21-13 | L00251 | | WHT | | | | SP01336 | | 9 | | ALL |
| K-A | | | | | 0-0 | 33-21-13 | L00252 | | BLK | | | | SP01338 | | 9 | | ALL |
| K-B | | | | | 0-0 | 33-21-13 | L00252 | | BLK | | | | SP01340 | | 9 | | ALL |
| K-C | | | | | 0-0 | 33-21-13 | L00252 | | WHT | | | | SP01342 | | 9 | | ALL |
| K-D | | | | | 0-0 | 33-21-13 | L00252 | | WHT | | | | SP01344 | | 9 | | ALL |
| L-A | | | | | 0-0 | 33-21-13 | L00253 | | BLK | | | | SP01346 | | 9 | | ALL |
| L-B | | | | | 0-0 | 33-21-13 | L00253 | | BLK | | | | SP01348 | | 9 | | ALL |
| L-C | | | | | 0-0 | 33-21-13 | L00253 | | WHT | | | | SP01350 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0810
 Page 46
 Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0812 | 286T0812 | | | CEILING LTS,FWD & MID INDIRECT & DIRECT (continued) | | | | | | | | | | | | | |
| L-D | | | | 0-0 | 33-21-13 | L00253 | | WHT | | | | | SP01352 | | 9 | | ALL |
| M-A | | | | 0-0 | 33-21-13 | L00254 | | BLK | | | | | SP01354 | | 9 | | ALL |
| M-B | | | | 0-0 | 33-21-13 | L00254 | | BLK | | | | | SP01356 | | 9 | | ALL |
| M-C | | | | 0-0 | 33-21-13 | L00254 | | WHT | | | | | SP01358 | | 9 | | ALL |
| M-D | | | | 0-0 | 33-21-13 | L00254 | | WHT | | | | | SP01360 | | 9 | | ALL |
| N-A | | | | 0-0 | 33-21-13 | L00255 | | BLK | | | | | SP01362 | | 9 | | ALL |
| N-B | | | | 0-0 | 33-21-13 | L00255 | | BLK | | | | | SP01364 | | 9 | | ALL |
| N-C | | | | 0-0 | 33-21-13 | L00255 | | WHT | | | | | SP01366 | | 9 | | ALL |
| N-D | | | | 0-0 | 33-21-13 | L00255 | | WHT | | | | | SP01368 | | 9 | | ALL |
| P-A | | | | 0-0 | 33-21-13 | L00282 | | BLK | | | | | SP01370 | | 9 | | 050-099 |
| P-B | | | | 0-0 | 33-21-13 | L00282 | | BLK | | | | | SP01372 | | 9 | | 050-099 |
| P-C | | | | 0-0 | 33-21-13 | L00282 | | WHT | | | | | SP01374 | | 9 | | 050-099 |
| P-D | | | | 0-0 | 33-21-13 | L00282 | | WHT | | | | | SP01376 | | 9 | | 050-099 |
| R-A | | | | 0-0 | 33-21-13 | L00283 | | BLK | | | | | SP01378 | | 9 | | 050-099 |
| R-B | | | | 0-0 | 33-21-13 | L00283 | | BLK | | | | | SP01380 | | 9 | | 050-099 |
| R-C | | | | 0-0 | 33-21-13 | L00283 | | WHT | | | | | SP01382 | | 9 | | 050-099 |
| R-D | | | | 0-0 | 33-21-13 | L00283 | | WHT | | | | | SP01384 | | 9 | | 050-099 |
| S-A | | | | 0-0 | 33-21-11 | L00247 | | BLK | | | | | SP00808 | | 9 | | 050-099 |
| S-A | | | | 0-0 | 33-21-13 | L00247 | | BLK | | | | | SP00808 | | 9 | | 150-199, 275-278 |
| S-B | | | | 0-0 | 33-21-11 | L00247 | | BLK | | | | | SP00810 | | 9 | | 050-099 |
| S-B | | | | 0-0 | 33-21-13 | L00247 | | BLK | | | | | SP00810 | | 9 | | 150-199, 275-278 |
| S-C | | | | 0-0 | 33-21-11 | L00247 | | WHT | | | | | SP00804 | | 9 | | 050-099 |
| S-C | | | | 0-0 | 33-21-13 | L00247 | | WHT | | | | | SP00804 | | 9 | | 150-199, 275-278 |
| S-D | | | | 0-0 | 33-21-11 | L00247 | | WHT | | | | | SP00806 | | 9 | | 050-099 |
| S-D | | | | 0-0 | 33-21-13 | L00247 | | WHT | | | | | SP00806 | | 9 | | 150-199, 275-278 |
| W0813 | 286T0813 | | | SATCOM SYSTEM SIDE-MOUNTED HGA SUBSYSTEM-STRBD | | | | | | | | | | | | | |
| 001 | 20 | | PA | 38-0 | 23-25-17 | D02717 | | F | | | | | D06173J | | 1 | | 156-157, 166-199, 277-299 |
| 002 | 20 | | PA | 40-0 | 23-25-17 | D02689 | | M | | | | | D06173J | | 4 | | 156-157, 166-199, 277-299 |
| 003 | 20 | | PA | 11-0 | 23-25-17 | D02717 | | E | | | | | GD01750 | A.. | 2 | | 156-157, 166-199, 277-299 |
| 004 | 20 | | PA | 11-0 | 23-25-17 | D02717 | | A | | | | | GD01750 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 010 | 20 | | PA | 3-0 | 23-25-17 | D02689 | | L | | | | | GD06889 | A.. | 2 | | 156-157, 166-199 |
| 010 | 20 | | PA | 3-0 | 23-25-17 | D02689 | | L | | | | | STA1109 | REF | = | | 277-299 |
| 011 | 20 | | PA | 3-0 | 23-25-17 | D02689 | | B- | | | | | GD06889 | S.. | 2 | | 156-157, 166-199 |
| 011 | 20 | | PA | 3-0 | 23-25-17 | D02689 | | B- | | | | | STA1109 | REF | = | | 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 47

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0813 | 286T0813 | | | SATCOM SYSTEM SIDE-MOUNTED HGA SUBSYSTEM-STRBD (continued) | | | | | | | | | | | |
| 012 | 24 | | PK | 1-0 | 23-25-17 | D02689 | | B | | | SM00001 | | | W | 156-157, 166-199, 277-299 |
| 013 | 24 | | PK | 6-0 | 23-25-17 | D02689 | | C- | | | D02717 | | | H | 156-157, 166-199, 277-299 |
| 014 | 24 | | PK | 6-0 | 23-25-17 | D02689 | | A- | | | D02717 | | | B | 156-157, 166-199, 277-299 |
| 015 | 24 | | PK | 13-0 | 23-25-17 | D02689 | | Y | | | SP00527 | | | 9 | 156-157, 166-199, 277-299 |
| 016 | 24 | | PK | 6-0 | 23-25-17 | D02689 | | CAP | Y | | D02717 | | | J | 156-157, 166-199, 277-299 |
| 017 | 24 | | PK | 1-0 | 23-25-17 | D02689 | | C | | | SM00001 | | | W | 156-157, 166-199, 277-299 |
| 018 | 24 | | PK | 1-0 | 23-25-17 | D02689 | | D | | | SM00001 | | | W | 156-157, 166-199, 277-299 |
| 201B | 24 | PL | IA | 40-0 | 23-25-17 | D02689 | | H | | | D06173J | | | 2 | 156-157, 166-199, 277-299 |
| 201R | 24 | PL | IA | 0-0 | 23-25-17 | D02689 | | G | | | D06173J | | | 3 | 156-157, 166-199, 277-299 |
| 202 | 20 | UA | | 1-6 | 23-25-17 | D02689 | | REF | | IB | GD06889 | | S.. | 2 | 156-157, 166-199 |
| 202 | 20 | UA | | 1-6 | 23-25-17 | D02689 | | REF | | IB | STA1109 | | REF | = | 277-299 |
| 202B | 24 | PW | IB | 40-0 | 23-25-17 | D02689 | | U | | | D06173J | | | 5 | 156-157, 166-199, 277-299 |
| 202R | 24 | PW | IB | 0-0 | 23-25-17 | D02689 | | T | | | D06173J | | | 6 | 156-157, 166-199, 277-299 |
| 202Z | | | IB | 0-0 | 23-25-17 | D02689 | | REF | | IB | D06173J | | | 7 | 156-157, 166-199, 277-299 |
| 203 | 20 | UA | | 1-6 | 23-25-17 | D02689 | | REF | | IC | GD06889 | | S.. | 2 | 156-157, 166-199 |
| 203 | 20 | UA | | 1-6 | 23-25-17 | D02689 | | REF | | IC | STA1109 | | REF | = | 277-299 |
| 203B | 24 | PW | IC | 40-0 | 23-25-17 | D02689 | | X | | | D06173J | | | 8 | 156-157, 166-199, 277-299 |
| 203R | 24 | PW | IC | 0-0 | 23-25-17 | D02689 | | W | | | D06173J | | | 9 | 156-157, 166-199, 277-299 |
| 203Z | | | IC | 0-0 | 23-25-17 | D02689 | | REF | | IC | D06173J | | | 10 | 156-157, 166-199, 277-299 |
| 204 | 20 | UA | | 1-6 | 23-25-17 | D02689 | | REF | | ID | GD06889 | | S.. | 2 | 156-157, 166-199 |
| 204 | 20 | UA | | 1-6 | 23-25-17 | D02689 | | REF | | ID | STA1109 | | REF | = | 277-299 |
| 204B | 24 | PW | ID | 40-0 | 23-25-17 | D02689 | | R | | | D06173J | | | 11 | 156-157, 166-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 48
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-------|---|----------|-------|------|------|--------|----------|------|------|--------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0813 | 286T0813 | | | | SATCOM SYSTEM SIDE-MOUNTED HGA SUBSYSTEM-STRBD (continued) | | | | | | | | | | |
| 204R | 24 | PW | ID | 0-0 | 23-25-17 | D02689 | | P | | | D06173J | 12 | | | 156-157, 166-199, 277-299 |
| 204Z | | | ID | 0-0 | 23-25-17 | D02689 | | REF | ID | | D06173J | 13 | | | 156-157, 166-199, 277-299 |
| 205B | 24 | PL | IE | 40-0 | 23-25-17 | D02689 | | F | | | D06173J | 14 | | | 156-157, 166-199, 277-299 |
| 205R | 24 | PL | IE | 0-0 | 23-25-17 | D02689 | | E | | | D06173J | 15 | | | 156-157, 166-199, 277-299 |
| W0814 | 286T0814 | | | | MID GALLEY & SIDEWALL WASH LTS | | | | | | | | | | |
| 002 | 22 | PA | | 24-0 | 33-26-11 | SM00038 | | | 9 | | D05116P | 2 | | | 050-099 |
| 002 | 22 | PA | | 3-0 | 33-26-11 | D05114P | 2 | | | | SP03632 | | 9 | | 150-199 |
| 002 | 22 | PA | | 80-6 | 33-26-11 | D05114P | 2 | | | | D05116P | 2 | | | 275-278 |
| 002 | 22 | PA | | 80-1 | 33-26-11 | D05114P | 2 | | | | D05116P | 2 | | | 280-299 |
| 003 | 16 | PA | | 5-0 | 38-13-11 | D00812 | | 8 | | | SM00034 | | 9 | | 050-099 |
| 003 | 16 | PA | | 15-1 | 38-13-11 | SP00489 | | | 9 | | D00812 | 8 | | | 150-199 |
| 003 | 16 | PA | | 37-10 | 38-13-11 | SM00034 | | | 9 | | D00812 | 8 | | | 275-278 |
| 003 | 16 | PA | | 58-4 | 38-13-11 | SM00034 | | | 9 | | D00812 | 8 | | | 280-299 |
| 011 | 16 | PA | | 72-0 | 38-13-11 | D05114P | 21 | FL | | | D05116P | 11 | FM | | 050-099 |
| 011 | 16 | PA | | 80-6 | 38-13-11 | D05114P | 40 | | | | D05116P | 23 | | | 150-157 |
| 011 | 16 | PA | | 80-6 | 38-13-11 | D05114P | 31 | | | | D05116P | 23 | | | 162-199 |
| 011 | 16 | PA | | 80-6 | 38-13-11 | D05114P | 43 | | | | D05116P | 11 | | | 275-278 |
| 011 | 16 | PA | | 80-1 | 38-13-11 | D05114P | 43 | | | | D05116P | 11 | | | 280-299 |
| 013 | 22 | PA | | 11-0 | 33-25-11 | D00812 | | 25 | | | SP00570 | | S | | 050-099 |
| 013 | 22 | PA | | 84-0 | 33-25-11 | D00812 | | 25 | | | SP00576 | | S | | 150-199 |
| 01C | 20 | PA | | 21-11 | SPARE | D13484 | | 1 | | | D72046 | 1 | | | 280-299 |
| 01D | 20 | PA | | 21-11 | SPARE | D13484 | | 2 | | | D72046 | 2 | | | 280-299 |
| 01E | 20 | PA | | 21-11 | SPARE | D13484 | | 3 | | | D72046 | 3 | | | 280-299 |
| 01F | 20 | PA | | 21-11 | SPARE | D13484 | | 4 | | | D72046 | 4 | | | 280-299 |
| 01G | 20 | PA | | 21-11 | SPARE | D13484 | | 5 | | | D72046 | 5 | | | 280-299 |
| 01H | 20 | PA | | 21-11 | SPARE | D13484 | | 6 | | | D72046 | 6 | | | 280-299 |
| 01J | 20 | PA | | 7-1 | SPARE | D13484 | | 7 | | | SM00085 | | S | | 280-299 |
| 01K | 20 | PA | | 9-9 | SPARE | D13484 | | 8 | | | GD04970 | D.. | E | | 280-299 |
| 01L | 20 | PA | | 7-3 | SPARE | D72048 | | 1 | | | SM00085 | | S | | 280-299 |
| 01M | 20 | PA | | 9-11 | SPARE | D72048 | | 2 | | | GD04970 | D.. | E | | 280-299 |
| 01N | 20 | PA | | 11-0 | SPARE | STA0631L | | CAP | * | | STA0654L | CAP | Y | | 280-299 |
| 01P | 20 | PA | | 12-10 | 33-51-12 | L00294 | | 1 | C | | SM00085 | | S | | 280-299 |
| 020 | 20 | PA | | 28-0 | 25-42-11 | D05116P | | 12 | | | SM00045 | | 9 | | 050-099 |
| 020 | 20 | PA | | 19-7 | 25-42-11 | D05116P | | 11 | | | SM00045 | | 9 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 49

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|---------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | |
| 020 | 20 | | PA | | 19-7 25-42-11 | D05116P | | 12 | | | SM00045 | | 9 | | 275-278 |
| 020 | 20 | | PA | | 76-8 25-42-11 | D05116P | | 12 | | | SM00045 | | 9 | | 280-299 |
| 021 | 20 | | PA | | 72-0 33-27-11 | D05114P | | 5 | | | D05116P | | 4 | | 050-099 |
| 021 | 20 | | PA | | 80-6 33-27-11 | D05114P | | 5 | | | D05116P | | 4 | | 150-199, 275-278 |
| 021 | 20 | | PA | | 80-1 33-27-11 | D05114P | | 5 | | | D05116P | | 4 | | 280-299 |
| 022 | 20 | | PA | | 80-6 33-21-35 | D05114P | | 18 | | | D05116P | | 19 | | 150-154, 157-165, 167-199, 275-278 |
| 022 | 20 | | PQ | AY | 80-6 33-21-35 | D05114P | | 18 | | | D05116P | | 19 | | 155-156, 166 |
| 022 | 20 | | PA | | 80-1 33-21-35 | D05114P | | 18 | | | D05116P | | 19 | | 280-299 |
| 022Z | | | | AY | 0-0 33-21-35 | D05114P | | DED | | | D05116P | | DED | | 155-156, 166 |
| 029 | 20 | | PA | | 3-4 33-21-33 | GD05304 | | A.. | E | | D02008 | | 7 | | 150-154, 157-165, 167-199 |
| 029 | 20 | | PQ | BD | 3-4 33-21-33 | GD05304 | | A.. | E | | D02008 | | 7 | | 155-156, 166 |
| 029Z | | | | BD | 0-0 33-21-33 | GD05304 | | DED | | | D02008 | | DED | | 155-156, 166 |
| 030 | 20 | | PA | | 3-4 33-21-33 | GD05306 | | S.. | E | | D02008 | | 8 | | 150-199 |
| 037 | 22 | | PA | | 25-8 33-21-33 | D02008 | | 2 | | | D03086 | | 1 | | 150-199 |
| 038 | 22 | | PA | | 25-8 33-21-33 | D02008 | | 3 | | | D03086 | | 2 | | 150-199 |
| 039 | 22 | | PA | | 18-9 33-21-33 | SM00008 | | | 9 | | D03086 | | 3 | | 150-199 |
| 040 | 22 | | PA | | 18-9 33-21-33 | SM00009 | | | 9 | | D03086 | | 4 | | 150-199 |
| 041 | 22 | | PA | | 10-6 33-21-33 | SM00008 | | | 9 | | D03118 | | 3 | | 150-199 |
| 042 | 22 | | PA | | 10-6 33-21-33 | SM00009 | | | 9 | | D03118 | | 4 | | 150-199 |
| 043 | 22 | | PA | | 11-8 33-21-33 | D02008 | | | 9 | | D03118 | | 1 | | 150-199 |
| 044 | 22 | | PA | | 11-8 33-21-33 | D02008 | | | 10 | | D03118 | | 2 | | 150-199 |
| 045 | 22 | | PA | | 9-3 33-21-33 | D02008 | | | 11 | | SM00008 | | 9 | | 150-199 |
| 046 | 22 | | PA | | 9-3 33-21-33 | D02008 | | | 12 | | SM00009 | | 9 | | 150-199 |
| 047 | 22 | | PA | | 55-0 33-21-35 | D05114P | | | 11 | | D02010 | | 5 | | 050-099 |
| 047 | 16 | | PA | | 67-8 33-21-35 | D05114P | | | 27 | | D02010 | | 5 | FM | 150-154, 157-165, 167-199 |
| 047 | 16 | | PQ | U | 67-8 33-21-35 | D05114P | | | 27 | | D02010 | | 5 | FM | 155-156, 166 |
| 047 | 16 | | PA | | 72-3 33-21-35 | D05114P | | | 27 | | D02010 | | 5 | FM | 275-278 |
| 047 | 16 | | PA | | 72-7 33-21-35 | D05114P | | | 27 | | D02010 | | 5 | FM | 280-299 |
| 047Z | | | | U | 0-0 33-21-35 | D05114P | | DED | | | D02010 | | DED | | 155-156, 166 |
| 048 | 20 | | PA | | 3-0 33-21-35 | GD01460 | | A.. | E | | D02010 | | 7 | | 050-099 |
| 048 | 16 | | PA | | 9-4 33-21-35 | GD04916 | | A.. | E | | D02010 | | 7 | FM | 150-154, 157-165, 167-199 |
| 048 | 16 | | PQ | BW | 9-4 33-21-35 | GD04916 | | A.. | E | | D02010 | | 7 | FM | 155-156, 166 |
| 048 | 16 | | PA | | 3-8 33-21-35 | GD04916 | | A.. | E | | D02010 | | 7 | FM | 275-278 |
| 048 | 16 | | PA | | 4-0 33-21-35 | GD04916 | | A.. | E | | D02010 | | 7 | FM | 280-299 |
| 048Z | | | | BW | 0-0 33-21-35 | GD04916 | | DED | | | D02010 | | DED | | 155-156, 166 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 50

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 049 | 20 | | PA | 3-0 | 33-21-35 | GD02950 | | S.. | E | | | | D02010 | 8 | | | 050-099 |
| 049 | 16 | | PA | 9-4 | 33-21-35 | GD04920 | | S.. | E | | | | D02010 | 8 | FM | | 150-199 |
| 049 | 16 | | PA | 3-8 | 33-21-35 | GD04920 | | S.. | E | | | | D02010 | 8 | FM | | 275-278 |
| 049 | 16 | | PA | 4-0 | 33-21-35 | GD04920 | | S.. | E | | | | D02010 | 8 | FM | | 280-299 |
| 050 | 20 | | PA | 71-10 | 33-21-35 | D05114P | | | | 11 | | | D00926 | 5 | | | 275-299 |
| 051 | 20 | | PA | 3-4 | 33-21-35 | GD04916 | | A.. | E | | | | D00926 | 7 | | | 275-299 |
| 052 | 20 | | PA | 3-4 | 33-21-35 | GD04920 | | S.. | E | | | | D00926 | 8 | | | 275-299 |
| 053 | 22 | | PA | 13-0 | 33-21-35 | D02010 | | | | 2 | | | D03120 | 1 | | | 050-099 |
| 053 | 22 | | PA | 6-7 | 33-21-35 | D02010 | | | | 2 | | | D03120 | 1 | | | 150-199 |
| 053 | 22 | | PA | 14-0 | 33-21-35 | D02010 | | | | 2 | | | D03120 | 1 | | | 275-278 |
| 053 | 22 | | PA | 14-5 | 33-21-35 | D02010 | | | | 2 | | | D03120 | 1 | | | 280-299 |
| 054 | 22 | | PA | 13-0 | 33-21-35 | D02010 | | | | 3 | | | D03120 | 2 | | | 050-099 |
| 054 | 22 | | PA | 6-7 | 33-21-35 | D02010 | | | | 3 | | | D03120 | 2 | | | 150-199 |
| 054 | 22 | | PA | 14-0 | 33-21-35 | D02010 | | | | 3 | | | D03120 | 2 | | | 275-278 |
| 054 | 22 | | PA | 14-5 | 33-21-35 | D02010 | | | | 3 | | | D03120 | 2 | | | 280-299 |
| 055 | 22 | | PA | 8-0 | 33-21-35 | SM00004 | | | | | 9 | | D03120 | 3 | | | 050-099 |
| 055 | 22 | | PA | 9-8 | 33-21-35 | SM00004 | | | | | 9 | | D03120 | 3 | | | 150-199, 275-299 |
| 056 | 22 | | PA | 8-0 | 33-21-35 | SM00005 | | | | | 9 | | D03120 | 4 | | | 050-099 |
| 056 | 22 | | PA | 9-8 | 33-21-35 | SM00005 | | | | | 9 | | D03120 | 4 | | | 150-199, 275-299 |
| 057 | 22 | | PA | 7-0 | 33-21-35 | D02010 | | | | 11 | | | SM00004 | | 9 | | 050-099 |
| 057 | 22 | | PA | 6-9 | 33-21-35 | D02010 | | | | 11 | | | SM00004 | | 9 | | 150-199 |
| 057 | 22 | | PA | 11-4 | 33-21-35 | D02010 | | | | 11 | | | SM00004 | | 9 | | 275-278 |
| 057 | 22 | | PA | 11-8 | 33-21-35 | D02010 | | | | 11 | | | SM00004 | | 9 | | 280-299 |
| 058 | 22 | | PA | 7-0 | 33-21-35 | D02010 | | | | 12 | | | SM00005 | | 9 | | 050-099 |
| 058 | 22 | | PA | 6-9 | 33-21-35 | D02010 | | | | 12 | | | SM00005 | | 9 | | 150-199 |
| 058 | 22 | | PA | 11-4 | 33-21-35 | D02010 | | | | 12 | | | SM00005 | | 9 | | 275-278 |
| 058 | 22 | | PA | 11-8 | 33-21-35 | D02010 | | | | 12 | | | SM00005 | | 9 | | 280-299 |
| 059 | 22 | | PA | 11-0 | 33-21-35 | SM00004 | | | | | 9 | | D03122 | 3 | | | 050-099 |
| 059 | 22 | | PA | 11-0 | 33-21-35 | SM00006 | | | | | 9 | | D03122 | 3 | | | 275-299 |
| 060 | 22 | | PA | 11-0 | 33-21-35 | SM00005 | | | | | 9 | | D03122 | 4 | | | 050-099 |
| 060 | 22 | | PA | 11-0 | 33-21-35 | SM00007 | | | | | 9 | | D03122 | 4 | | | 275-299 |
| 061 | 22 | | PA | 17-0 | 33-21-35 | D02010 | | | | 9 | | | D03122 | 1 | | | 050-099 |
| 061 | 22 | | PA | 7-0 | 33-21-35 | D00926 | | | | 9 | | | D03122 | 1 | | | 275-299 |
| 062 | 22 | | PA | 17-0 | 33-21-35 | D02010 | | | | 10 | | | D03122 | 2 | | | 050-099 |
| 062 | 22 | | PA | 7-0 | 33-21-35 | D00926 | | | | 10 | | | D03122 | 2 | | | 275-299 |
| 063 | 22 | | PA | 13-5 | 33-21-35 | D00926 | | | | 2 | | | D03124 | 1 | | | 275-299 |
| 064 | 22 | | PA | 13-5 | 33-21-35 | D00926 | | | | 3 | | | D03124 | 2 | | | 275-299 |
| 065 | 22 | | PA | 6-2 | 33-21-35 | SM00006 | | | | | 9 | | D03124 | 3 | | | 275-299 |
| 066 | 22 | | PA | 6-2 | 33-21-35 | SM00007 | | | | | 9 | | D03124 | 4 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 51

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | |
| 071 | 22 | | PA | 8-3 | 33-21-35 | D00926 | | 11 | | | SM00006 | | 9 | | 275-299 |
| 072 | 22 | | PA | 8-3 | 33-21-35 | D00926 | | 12 | | | SM00007 | | 9 | | 275-299 |
| 073 | 22 | | PA | 72-0 | 33-21-35 | D05114P | | 12 | | | D05116P | | 7 | | 050-099 |
| 073 | 20 | | PA | 80-6 | 33-21-35 | D05114P | | 12 | | | D05116P | | 7 | | 150-154, 157-165, 167-199, 275-278 |
| 073 | 20 | | PQ | CW | 80-6 | 33-21-35 | | 12 | | | D05116P | | 7 | | 155-156, 166 |
| 073 | 20 | | PA | 80-1 | 33-21-35 | D05114P | | 12 | | | D05116P | | 7 | | 280-299 |
| 073Z | | | | CW | 0-0 | 33-21-35 | | DED | | | D05116P | | DED | | 155-156, 166 |
| 074 | 20 | | PA | 26-0 | 33-21-33 | D05114P | | 13 | | | D02950 | | 5 | | 050-099 |
| 074 | 20 | | PA | 24-5 | 33-21-33 | D05114P | | 13 | | | D02950 | | 5 | | 150-154, 157-165, 167-199, 275-278 |
| 074 | 20 | | PQ | CX | 24-5 | 33-21-33 | | 13 | | | D02950 | | 5 | | 155-156, 166 |
| 074 | 20 | | PA | 25-0 | 33-21-33 | D05114P | | 13 | | | D02950 | | 5 | | 280-299 |
| 074Z | | | | CX | 0-0 | 33-21-33 | | DED | | | D02950 | | DED | | 155-156, 166 |
| 077 | 20 | | PA | 4-0 | 33-21-33 | GD01592 | | A.. | E | | D02950 | | 7 | | 050-099 |
| 077 | 20 | | PA | 2-11 | 33-21-33 | GD01592 | | A.. | E | | D02950 | | 7 | | 150-154, 157-165, 167-199, 275-278 |
| 077 | 20 | | PQ | DB | 2-11 | 33-21-33 | | A.. | E | | D02950 | | 7 | | 155-156, 166 |
| 077 | 20 | | PA | | 2-9 | 33-21-33 | | A.. | E | | D02950 | | 7 | | 280-299 |
| 077Z | | | | DB | 0-0 | 33-21-33 | | DED | | | D02950 | | DED | | 155-156, 166 |
| 078 | 20 | | PA | | 4-0 | 33-21-33 | | S.. | E | | D02950 | | 8 | | 050-099 |
| 078 | 20 | | PA | | 2-11 | 33-21-33 | | S.. | E | | D02950 | | 8 | | 150-199, 275-278 |
| 078 | 20 | | PA | | 2-9 | 33-21-33 | | S.. | E | | D02950 | | 8 | | 280-299 |
| 079 | 22 | | PA | | 51-0 | 33-21-33 | | | | | D02950 | | 2 | | 050-099 |
| 079 | 22 | | PA | | 20-7 | 33-21-33 | | | | | D03106 | | 1 | | 150-199, 275-278 |
| 079 | 22 | | PA | | 20-1 | 33-21-33 | | | | | D02950 | | 2 | | 280-299 |
| 080 | 22 | | PA | | 51-0 | 33-21-33 | | | | | D02950 | | 3 | | 050-099 |
| 080 | 22 | | PA | | 20-7 | 33-21-33 | | | | | D03106 | | 2 | | 150-199, 275-278 |
| 080 | 22 | | PA | | 20-1 | 33-21-33 | | | | | D02950 | | 3 | | 280-299 |
| 081 | 22 | | PA | | 49-0 | 33-21-33 | | | 9 | | SM00019 | | 3 | | 050-099 |
| 081 | 22 | | PA | | 19-1 | 33-21-33 | | | 9 | | SM00019 | | 3 | | 150-199 |
| 081 | 22 | | PA | | 18-1 | 33-21-33 | | | 9 | | SM00019 | | 3 | | 275-278 |
| 081 | 22 | | PA | | 19-0 | 33-21-33 | | | 9 | | SM00019 | | 3 | | 280-299 |
| 082 | 22 | | PA | | 48-0 | 33-21-33 | | | 9 | | SM00020 | | 4 | | 050-099 |
| 082 | 22 | | PA | | 19-1 | 33-21-33 | | | 9 | | SM00020 | | 4 | | 150-199 |
| 082 | 22 | | PA | | 18-1 | 33-21-33 | | | 9 | | SM00020 | | 4 | | 275-278 |
| 082 | 22 | | PA | | 19-0 | 33-21-33 | | | 9 | | SM00020 | | 4 | | 280-299 |
| 083 | 18 | | PA | | 18-0 | 33-21-33 | | | 42 | | D05114P | | 5 | DK | 050-099 |
| 083 | 20 | | PA | | 17-2 | 33-21-33 | | | 14 | | D05114P | | 5 | | 150-154, 157, 163-165 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 52

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|----------|---------|---------|-------|-------|------|--------|-------|------|------|---------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | |
| 083 | 20 | PQ | DH | 17-2 | 33-21-33 | D05114P | | 14 | | | D02110 | 5 | | | 155-156, 166 |
| 083 | 16 | PA | | 17-2 | 33-21-33 | D05114P | | 29 | | | D02110 | 5 | FM | | 162, 167-199 |
| 083 | 16 | PA | | 16-4 | 33-21-33 | D05114P | | 42 | | | D02110 | 5 | FM | | 275-278 |
| 083 | 16 | PA | | 17-0 | 33-21-33 | D05114P | | 42 | | | D02110 | 5 | FM | | 280-299 |
| 083Z | | | DH | 0-0 | 33-21-33 | D05114P | | | DED | | D02110 | | DED | | 155-156, 166 |
| 084 | 18 | PA | | 8-0 | 33-21-33 | GD00938 | | | S.. 2 | | D02110 | 8 | DK | | 050-099 |
| 084 | 20 | PA | | 3-3 | 33-21-33 | GD00938 | | | S.. 2 | | D02110 | 8 | | | 150-157 |
| 084 | 16 | PA | | 3-3 | 33-21-33 | GD00938 | | | S.. 2 | | D02110 | 8 | FM | | 162-165 |
| 084 | 16 | PA | | 7-7 | 33-21-33 | GD00938 | | | S.. 2 | | D02110 | 8 | FM | | 166-199 |
| 084 | 16 | PA | | 6-9 | 33-21-33 | GD00938 | | | S.. 2 | | D02110 | 8 | FM | | 275-278 |
| 084 | 16 | PA | | 7-10 | 33-21-33 | GD00938 | | | S.. 2 | | D02110 | 8 | FM | | 280-299 |
| 085 | 18 | PA | | 8-0 | 33-21-33 | GD00938 | | | A.. 2 | | D02110 | 7 | DK | | 050-099 |
| 085 | 20 | PA | | 3-3 | 33-21-33 | GD00938 | | | A.. 2 | | D02110 | 7 | | | 150-154, 157, 163-165 |
| 085 | 20 | PQ | DJ | 3-3 | 33-21-33 | GD00938 | | | A.. 2 | | D02110 | 7 | | | 155-156 |
| 085 | 16 | PA | | 3-3 | 33-21-33 | GD00938 | | | A.. 2 | | D02110 | 7 | FM | | 162 |
| 085 | 20 | PQ | DJ | 7-7 | 33-21-33 | GD00938 | | | A.. 2 | | D02110 | 7 | | | 166 |
| 085 | 20 | PA | | 7-7 | 33-21-33 | GD00938 | | | A.. 2 | | D02110 | 7 | | | 167-199 |
| 085 | 16 | PA | | 6-9 | 33-21-33 | GD00938 | | | A.. 2 | | D02110 | 7 | FM | | 275-278 |
| 085 | 16 | PA | | 7-10 | 33-21-33 | GD00938 | | | A.. 2 | | D02110 | 7 | FM | | 280-299 |
| 085Z | | | DJ | 0-0 | 33-21-33 | GD00938 | | | DED | | D02110 | | DED | | 155-156, 166 |
| 086 | 20 | PA | | 42-0 | 33-21-33 | D05114P | | 15 | | | D02938 | 5 | | | 050-099 |
| 086 | 20 | PA | | 54-9 | 33-21-33 | D05114P | | 21 | | | D02938 | 5 | | | 150-154, 157-165, 167-199, 275-278 |
| 086 | 20 | PQ | DK | 54-9 | 33-21-33 | D05114P | | 21 | | | D02938 | 5 | | | 155-156, 166 |
| 086 | 20 | PA | | 55-0 | 33-21-33 | D05114P | | 21 | | | D02938 | 5 | | | 280-299 |
| 086Z | | | DK | 0-0 | 33-21-33 | D05114P | | | DED | | D02938 | | DED | | 155-156, 166 |
| 087 | 20 | PA | | 34-0 | 33-21-33 | D05114P | | 9 | | | D01982 | 5 | | | 050-099 |
| 087 | 20 | PA | | 32-1 | 33-21-33 | D05114P | | 9 | | | D01982 | 5 | | | 150-154, 157-165, 167-199, 275-278 |
| 087 | 20 | PQ | DL | 32-1 | 33-21-33 | D05114P | | 9 | | | D01982 | 5 | | | 155-156, 166 |
| 087 | 20 | PA | | 32-4 | 33-21-33 | D05114P | | 9 | | | D01982 | 5 | | | 280-299 |
| 087Z | | | DL | 0-0 | 33-21-33 | D05114P | | | DED | | D01982 | | DED | | 155-156, 166 |
| 088 | 20 | PA | | 19-0 | 33-21-33 | D05114P | | 17 | | | D02948 | 5 | | | 050-099 |
| 088 | 20 | PA | | 23-6 | 33-21-33 | D05114P | | 17 | | | D02948 | 5 | | | 150-154, 157-165 |
| 088 | 20 | PQ | D | 23-6 | 33-21-33 | D05114P | | 17 | | | D02948 | 5 | | | 155-156 |
| 088 | 20 | PQ | D | 17-2 | 33-21-33 | D05114P | | 17 | | | D02948 | 5 | | | 166 |
| 088 | 20 | PA | | 17-2 | 33-21-33 | D05114P | | 17 | | | D02948 | 5 | | | 167-199, 275-278 |
| 088 | 20 | PA | | 17-10 | 33-21-33 | D05114P | | 17 | | | D02948 | 5 | | | 280-299 |
| 088Z | | | D | 0-0 | 33-21-33 | D05114P | | | DED | | D02948 | | DED | | 155-156, 166 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 53

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | |
| 089 | 20 | | PA | | 4-0 | 33-21-33 | GD00938 | | S.. | 2 | D02948 | | 8 | | 050-099 |
| 089 | 20 | | PA | | 12-4 | 33-21-33 | D02948 | | 8 | | GD00938 | | S.. | 2 | 153-165 |
| 089 | 20 | | PA | | 7-7 | 33-21-33 | D02948 | | 8 | | GD00938 | | S.. | 2 | 166-199 |
| 089 | 20 | | PA | | 3-3 | 33-21-33 | GD00938 | | S.. | 2 | D02948 | | 8 | | 275-278 |
| 089 | 20 | | PA | | 2-11 | 33-21-33 | GD00938 | | S.. | 2 | D02948 | | 8 | | 280-299 |
| 090 | 20 | | PA | | 4-0 | 33-21-33 | GD00938 | | A.. | 2 | D02948 | | 7 | | 050-099 |
| 090 | 20 | | PA | | 6-9 | 33-21-33 | GD01592 | | A.. | E | D02948 | | 7 | | 150-154, 157-165 |
| 090 | 20 | | PQ | DO | 6-9 | 33-21-33 | GD01592 | | A.. | E | D02948 | | 7 | | 155-156 |
| 090 | 20 | | PQ | DO | 7-7 | 33-21-33 | GD00938 | | A.. | 2 | D02948 | | 7 | | 166 |
| 090 | 20 | | PA | | 7-7 | 33-21-33 | GD00938 | | A.. | 2 | D02948 | | 7 | | 167-199 |
| 090 | 20 | | PA | | 3-3 | 33-21-33 | GD00938 | | A.. | 2 | D02948 | | 7 | | 275-278 |
| 090 | 20 | | PA | | 2-11 | 33-21-33 | GD00938 | | A.. | 2 | D02948 | | 7 | | 280-299 |
| 090Z | | | | DO | 0-0 | 33-21-33 | GD01592 | | DED | | D02948 | | DED | | 155-156, 166 |
| 091 | 22 | | PA | | 12-3 | 33-21-33 | D02110 | | | 2 | D03180 | | 1 | | 275-278 |
| 091 | 22 | | PA | | 13-0 | 33-21-33 | D02110 | | | 2 | D03180 | | 1 | | 280-299 |
| 092 | 22 | | PA | | 12-3 | 33-21-33 | D02110 | | | 3 | D03180 | | 2 | | 275-278 |
| 092 | 22 | | PA | | 13-0 | 33-21-33 | D02110 | | | 3 | D03180 | | 2 | | 280-299 |
| 093 | 22 | | PA | | 9-8 | 33-21-33 | SM00011 | | | 9 | D03180 | | 3 | | 275-278 |
| 093 | 22 | | PA | | 9-3 | 33-21-33 | SM00011 | | | 9 | D03180 | | 3 | | 280-299 |
| 094 | 22 | | PA | | 9-8 | 33-21-33 | SM00012 | | | 9 | D03180 | | 4 | | 275-278 |
| 094 | 22 | | PA | | 9-3 | 33-21-33 | SM00012 | | | 9 | D03180 | | 4 | | 280-299 |
| 097 | 22 | | PA | | 11-0 | 33-21-33 | D02110 | | | 9 | D03182 | | 1 | | 050-099 |
| 097 | 22 | | PA | | 7-2 | 33-21-33 | D02110 | | | 9 | D03182 | | 1 | | 150-165 |
| 097 | 22 | | PA | | 11-4 | 33-21-33 | D02110 | | | 9 | D03182 | | 1 | | 166-199 |
| 098 | 22 | | PA | | 11-0 | 33-21-33 | D02110 | | | 10 | D03182 | | 2 | | 050-099 |
| 098 | 22 | | PA | | 7-2 | 33-21-33 | D02110 | | | 10 | D03182 | | 2 | | 150-165 |
| 098 | 22 | | PA | | 11-4 | 33-21-33 | D02110 | | | 10 | D03182 | | 2 | | 166-199 |
| 099 | 22 | | PA | | 11-0 | 33-21-33 | D02110 | | | 11 | D03182 | | 3 | | 050-099 |
| 099 | 22 | | PA | | 7-2 | 33-21-33 | D02110 | | | 11 | D03182 | | 3 | | 150-165 |
| 099 | 22 | | PA | | 11-4 | 33-21-33 | D02110 | | | 11 | D03182 | | 3 | | 166-199 |
| 099 | 22 | | PA | | 3-1 | 33-21-33 | D02110 | | | 11 | SM00011 | | 9 | | 275-278 |
| 099 | 22 | | PA | | 4-3 | 33-21-33 | D02110 | | | 11 | SM00011 | | 9 | | 280-299 |
| 100 | 22 | | PA | | 11-0 | 33-21-33 | D02110 | | | 12 | D03182 | | 4 | | 050-099 |
| 100 | 22 | | PA | | 7-2 | 33-21-33 | D02110 | | | 12 | D03182 | | 4 | | 150-165 |
| 100 | 22 | | PA | | 11-4 | 33-21-33 | D02110 | | | 12 | D03182 | | 4 | | 166-199 |
| 100 | 22 | | PA | | 3-1 | 33-21-33 | D02110 | | | 12 | SM00012 | | 9 | | 275-278 |
| 100 | 22 | | PA | | 4-3 | 33-21-33 | D02110 | | | 12 | SM00012 | | 9 | | 280-299 |
| 101 | 22 | | PA | | 14-0 | 33-21-33 | D02948 | | | 2 | D03184 | | 1 | | 050-099 |
| 101 | 22 | | PA | | 12-2 | 33-21-33 | D02948 | | | 2 | D03184 | | 1 | | 150-157 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 54

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 101 | 22 | | PA | 12-2 | 33-21-33 | D02948 | | 9 | | | | | D03184 | 1 | | | 162-165 |
| 101 | 22 | | PA | 15-2 | 33-21-33 | D02948 | | 9 | | | | | D03184 | 1 | | | 166-199 |
| 101 | 22 | | PA | 13-6 | 33-21-33 | D02948 | | 2 | | | | | D03184 | 1 | | | 275-299 |
| 102 | 22 | | PA | 14-0 | 33-21-33 | D02948 | | 3 | | | | | D03184 | 2 | | | 050-099 |
| 102 | 22 | | PA | 12-2 | 33-21-33 | D02948 | | 3 | | | | | D03184 | 2 | | | 150-157 |
| 102 | 22 | | PA | 12-2 | 33-21-33 | D02948 | | 10 | | | | | D03184 | 2 | | | 162-165 |
| 102 | 22 | | PA | 15-2 | 33-21-33 | D02948 | | 10 | | | | | D03184 | 2 | | | 166-199 |
| 102 | 22 | | PA | 13-6 | 33-21-33 | D02948 | | 3 | | | | | D03184 | 2 | | | 275-299 |
| 103 | 22 | | PA | 14-0 | 33-21-33 | SM00013 | | | 9 | | | | D03184 | 3 | | | 050-099 |
| 103 | 22 | | PA | 11-2 | 33-21-33 | SM00013 | | | 9 | | | | D03184 | 3 | | | 150-163, 275-299 |
| 103 | 22 | | PA | 12-2 | 33-21-33 | D02948 | | 11 | | | | | D03184 | 3 | | | 164-165 |
| 103 | 22 | | PA | 15-2 | 33-21-33 | D02948 | | 11 | | | | | D03184 | 3 | | | 166-199 |
| 104 | 22 | | PA | 14-0 | 33-21-33 | SM00014 | | | 9 | | | | D03184 | 4 | | | 050-099 |
| 104 | 22 | | PA | 11-2 | 33-21-33 | SM00014 | | | 9 | | | | D03184 | 4 | | | 150-163, 275-299 |
| 104 | 22 | | PA | 12-2 | 33-21-33 | D02948 | | 12 | | | | | D03184 | 4 | | | 164-165 |
| 104 | 22 | | PA | 15-2 | 33-21-33 | D02948 | | 12 | | | | | D03184 | 4 | | | 166-199 |
| 105 | 22 | | PA | 62-0 | 33-21-33 | SM00013 | | | 9 | | | | D03102 | 3 | | | 050-099 |
| 105 | 22 | | PA | 17-11 | 33-21-33 | SM00013 | | | 9 | | | | D03102 | 3 | | | 150-157, 275-278 |
| 105 | 22 | | PA | 17-8 | 33-21-33 | SM00013 | | | 9 | | | | D03102 | 3 | | | 280-299 |
| 106 | 22 | | PA | 61-0 | 33-21-33 | SM00014 | | | 9 | | | | D03102 | 4 | | | 050-099 |
| 106 | 22 | | PA | 17-11 | 33-21-33 | SM00014 | | | 9 | | | | D03102 | 4 | | | 150-157, 275-278 |
| 106 | 22 | | PA | 17-8 | 33-21-33 | SM00014 | | | 9 | | | | D03102 | 4 | | | 280-299 |
| 107 | 22 | | PA | 65-0 | 33-21-33 | D02948 | | 9 | | | | | D03102 | 1 | | | 050-099 |
| 107 | 22 | | PA | 26-4 | 33-21-33 | D02948 | | 9 | | | | | D03102 | 1 | | | 150-157 |
| 107 | 22 | | PA | 20-3 | 33-21-33 | D02948 | | 9 | | | | | D03102 | 1 | | | 275-278 |
| 107 | 22 | | PA | 19-11 | 33-21-33 | D02948 | | 9 | | | | | D03102 | 1 | | | 280-299 |
| 108 | 22 | | PA | 65-0 | 33-21-33 | D02948 | | 10 | | | | | D03102 | 2 | | | 050-099 |
| 108 | 22 | | PA | 26-4 | 33-21-33 | D02948 | | 10 | | | | | D03102 | 2 | | | 150-157 |
| 108 | 22 | | PA | 20-3 | 33-21-33 | D02948 | | 10 | | | | | D03102 | 2 | | | 275-278 |
| 108 | 22 | | PA | 19-11 | 33-21-33 | D02948 | | 10 | | | | | D03102 | 2 | | | 280-299 |
| 109 | 22 | | PA | 5-0 | 33-21-33 | D02948 | | 11 | | | | | SM00013 | | 9 | | 050-099 |
| 109 | 22 | | PA | 10-10 | 33-21-33 | D02948 | | 11 | | | | | SM00013 | | 9 | | 150-163 |
| 109 | 22 | | PA | 2-10 | 33-21-33 | D02948 | | 11 | | | | | SM00013 | | 9 | | 275-299 |
| 110 | 22 | | PA | 5-0 | 33-21-33 | D02948 | | 12 | | | | | SM00014 | | 9 | | 050-099 |
| 110 | 22 | | PA | 10-10 | 33-21-33 | D02948 | | 12 | | | | | SM00014 | | 9 | | 150-163 |
| 110 | 22 | | PA | 2-10 | 33-21-33 | D02948 | | 12 | | | | | SM00014 | | 9 | | 275-299 |
| 111 | 20 | | PA | 5-0 | 33-21-33 | GD01614 | | S.. | E | | | | D02938 | 8 | | | 050-099 |
| 111 | 20 | | PA | 3-5 | 33-21-33 | GD04828 | | S.. | E | | | | D02938 | 8 | | | 150-199, 275-278 |
| 111 | 20 | | PA | 3-0 | 33-21-33 | GD04828 | | S.. | E | | | | D02938 | 8 | | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 55

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | |
| 112 | 20 | | PA | | 5-0 | 33-21-33 | GD01616 | A.. | E | | D02938 | | | | 050-099 |
| 112 | 20 | | PA | | 3-5 | 33-21-33 | GD04960 | A.. | E | | D02938 | | | | 150-154, 157-165, 167-199, 275-278 |
| 112 | 20 | | PQ | EL | 3-5 | 33-21-33 | GD04960 | A.. | E | | D02938 | | | | 155-156, 166 |
| 112 | 20 | | PA | | 3-2 | 33-21-33 | GD04960 | A.. | E | | D02938 | | | | 280-299 |
| 112Z | | | | EL | 0-0 | 33-21-33 | GD04960 | DED | | | D02938 | | DED | | 155-156, 166 |
| 113 | 20 | | PA | | 3-0 | 33-21-33 | GD01618 | S.. | E | | D01982 | | | | 050-099, 150-199, 275-278 |
| 113 | 20 | | PA | | 2-11 | 33-21-33 | GD01618 | S.. | E | | D01982 | | | | 280-299 |
| 114 | 20 | | PA | | 3-0 | 33-21-33 | GD01620 | A.. | E | | D01982 | | | | 050-099 |
| 114 | 20 | | PA | | 3-0 | 33-21-33 | GD01006 | A.. | E | | D01982 | | | | 150-154, 157-165, 167-199, 275-299 |
| 114 | 20 | | PQ | EN | 3-0 | 33-21-33 | GD01006 | A.. | E | | D01982 | | | | 155-156, 166 |
| 114Z | | | | EN | 0-0 | 33-21-33 | GD01006 | DED | | | D01982 | | DED | | 155-156, 166 |
| 115 | 22 | | PA | | 16-0 | 33-21-33 | D02938 | | 2 | | D03114 | | | | 050-099 |
| 115 | 22 | | PA | | 7-6 | 33-21-33 | D02938 | | 2 | | D03114 | | | | 150-199, 275-278 |
| 115 | 22 | | PA | | 7-4 | 33-21-33 | D02938 | | 2 | | D03114 | | | | 280-299 |
| 116 | 22 | | PA | | 16-0 | 33-21-33 | D02938 | | 3 | | D03114 | | | | 050-099 |
| 116 | 22 | | PA | | 7-6 | 33-21-33 | D02938 | | 3 | | D03114 | | | | 150-199, 275-278 |
| 116 | 22 | | PA | | 7-4 | 33-21-33 | D02938 | | 3 | | D03114 | | | | 280-299 |
| 117 | 22 | | PA | | 11-0 | 33-21-33 | SM00015 | | 9 | | D03114 | | | | 050-099 |
| 117 | 22 | | PA | | 6-2 | 33-21-33 | SM00015 | | 9 | | D03114 | | | | 150-199, 275-278 |
| 117 | 22 | | PA | | 8-1 | 33-21-33 | SM00015 | | 9 | | D03114 | | | | 280-299 |
| 118 | 22 | | PA | | 11-0 | 33-21-33 | SM00016 | | 9 | | D03114 | | | | 050-099 |
| 118 | 22 | | PA | | 6-2 | 33-21-33 | SM00016 | | 9 | | D03114 | | | | 150-199, 275-278 |
| 118 | 22 | | PA | | 8-1 | 33-21-33 | SM00016 | | 9 | | D03114 | | | | 280-299 |
| 119 | 22 | | PA | | 18-0 | 33-21-33 | SM00015 | | 9 | | D03082 | | | | 050-099 |
| 119 | 22 | | PA | | 20-6 | 33-21-33 | D03082 | | 3 | | SM00015 | | 9 | | 150-199, 275-278 |
| 119 | 22 | | PA | | 18-6 | 33-21-33 | D03082 | | 3 | | SM00015 | | 9 | | 280-299 |
| 120 | 22 | | PA | | 18-0 | 33-21-33 | SM00016 | | 9 | | D03082 | | 4 | | 050-099 |
| 120 | 22 | | PA | | 20-6 | 33-21-33 | D03082 | | 4 | | SM00016 | | 9 | | 150-199, 275-278 |
| 120 | 22 | | PA | | 18-6 | 33-21-33 | D03082 | | 4 | | SM00016 | | 9 | | 280-299 |
| 121 | 22 | | PA | | 22-0 | 33-21-33 | D02938 | | 9 | | D03082 | | | | 050-099 |
| 121 | 22 | | PA | | 23-3 | 33-21-33 | D03082 | | 1 | | D02938 | | 9 | | 150-199, 275-299 |
| 122 | 22 | | PA | | 22-0 | 33-21-33 | D02938 | | 10 | | D03082 | | | | 050-099 |
| 122 | 22 | | PA | | 23-3 | 33-21-33 | D03082 | | 2 | | D02938 | | 10 | | 150-199, 275-299 |
| 123 | 22 | | PA | | 6-0 | 33-21-33 | D02938 | | 11 | | SM00015 | | 9 | | 050-099 |
| 123 | 22 | | PA | | 3-3 | 33-21-33 | D02938 | | 11 | | SM00015 | | 9 | | 150-199, 275-278 |
| 123 | 22 | | PA | | 5-3 | 33-21-33 | D02938 | | 11 | | SM00015 | | 9 | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 56

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 124 | 22 | | PA | 6-0 | 33-21-33 | D02938 | | 12 | | | | | SM00016 | | 9 | | 050-099 |
| 124 | 22 | | PA | 3-3 | 33-21-33 | D02938 | | 12 | | | | | SM00016 | | 9 | | 150-199, 275-278 |
| 124 | 22 | | PA | 5-3 | 33-21-33 | D02938 | | 12 | | | | | SM00016 | | 9 | | 280-299 |
| 125 | 22 | | PA | 16-0 | 33-21-33 | D01982 | | 2 | | | | | D03192 | | 1 | | 050-099 |
| 125 | 22 | | PA | 13-10 | 33-21-33 | D01982 | | 2 | | | | | D03192 | | 1 | | 150-199, 275-278 |
| 125 | 22 | | PA | 14-8 | 33-21-33 | D01982 | | 2 | | | | | D03192 | | 1 | | 280-299 |
| 126 | 22 | | PA | 16-0 | 33-21-33 | D01982 | | 3 | | | | | D03192 | | 2 | | 050-099 |
| 126 | 22 | | PA | 13-10 | 33-21-33 | D01982 | | 3 | | | | | D03192 | | 2 | | 150-199, 275-278 |
| 126 | 22 | | PA | 14-8 | 33-21-33 | D01982 | | 3 | | | | | D03192 | | 2 | | 280-299 |
| 127 | 22 | | PA | 13-0 | 33-21-33 | SM00017 | | | 9 | | | | D03192 | | 3 | | 050-099 |
| 127 | 22 | | PA | 12-0 | 33-21-33 | SM00017 | | | 9 | | | | D03192 | | 3 | | 150-199, 275-278 |
| 127 | 22 | | PA | 10-3 | 33-21-33 | SM00017 | | | 9 | | | | D03192 | | 3 | | 280-299 |
| 128 | 22 | | PA | 13-0 | 33-21-33 | SM00018 | | | 9 | | | | D03192 | | 4 | | 050-099 |
| 128 | 22 | | PA | 12-0 | 33-21-33 | SM00018 | | | 9 | | | | D03192 | | 4 | | 150-199, 275-278 |
| 128 | 22 | | PA | 10-3 | 33-21-33 | SM00018 | | | 9 | | | | D03192 | | 4 | | 280-299 |
| 129 | 22 | | PA | 33-0 | 33-21-33 | SM00017 | | | 9 | | | | D03110 | | 3 | | 050-099 |
| 129 | 22 | | PA | 16-9 | 33-21-33 | SM00017 | | | 9 | | | | D03110 | | 3 | | 150-199, 275-278 |
| 129 | 22 | | PA | 18-10 | 33-21-33 | SM00017 | | | 9 | | | | D03110 | | 3 | | 280-299 |
| 130 | 22 | | PA | 33-0 | 33-21-33 | SM00018 | | | 9 | | | | D03110 | | 4 | | 050-099 |
| 130 | 22 | | PA | 16-9 | 33-21-33 | SM00018 | | | 9 | | | | D03110 | | 4 | | 150-199, 275-278 |
| 130 | 22 | | PA | 18-10 | 33-21-33 | SM00018 | | | 9 | | | | D03110 | | 4 | | 280-299 |
| 131 | 22 | | PA | 36-0 | 33-21-33 | D01982 | | 9 | | | | | D03110 | | 1 | | 050-099 |
| 131 | 22 | | PA | 19-10 | 33-21-33 | D01982 | | 9 | | | | | D03110 | | 1 | | 150-199, 275-278 |
| 131 | 22 | | PA | 20-0 | 33-21-33 | D01982 | | 9 | | | | | D03110 | | 1 | | 280-299 |
| 132 | 22 | | PA | 36-0 | 33-21-33 | D01982 | | 10 | | | | | D03110 | | 2 | | 050-099 |
| 132 | 22 | | PA | 19-10 | 33-21-33 | D01982 | | 10 | | | | | D03110 | | 2 | | 150-199, 275-278 |
| 132 | 22 | | PA | 20-0 | 33-21-33 | D01982 | | 10 | | | | | D03110 | | 2 | | 280-299 |
| 133 | 22 | | PA | 4-0 | 33-21-33 | D01982 | | 11 | | | | | SM00017 | | 9 | | 050-099 |
| 133 | 22 | | PA | 3-8 | 33-21-33 | D01982 | | 11 | | | | | SM00017 | | 9 | | 150-199, 275-278 |
| 133 | 22 | | PA | 4-11 | 33-21-33 | D01982 | | 11 | | | | | SM00017 | | 9 | | 280-299 |
| 134 | 22 | | PA | 4-0 | 33-21-33 | D01982 | | 12 | | | | | SM00018 | | 9 | | 050-099 |
| 134 | 22 | | PA | 3-8 | 33-21-33 | D01982 | | 12 | | | | | SM00018 | | 9 | | 150-199, 275-278 |
| 134 | 22 | | PA | 4-11 | 33-21-33 | D01982 | | 12 | | | | | SM00018 | | 9 | | 280-299 |
| 135 | 20 | | PA | 2-6 | 33-21-33 | GD02036 | | S.. | E | | | | D03180 | | 5 | | 275-299 |
| 136 | 20 | | PA | 3-0 | 33-21-33 | GD02038 | | S.. | E | | | | D03182 | | 5 | | 050-099 |
| 136 | 20 | | PA | 2-11 | 33-21-33 | GD02038 | | S.. | E | | | | D03182 | | 5 | | 150-199 |
| 137 | 20 | | PA | 3-0 | 33-21-33 | GD02040 | | S.. | E | | | | D03184 | | 5 | | 050-099 |
| 137 | 20 | | PA | 2-11 | 33-21-33 | GD02040 | | S.. | E | | | | D03184 | | 5 | | 150-199, 275-278 |
| 137 | 20 | | PA | 2-8 | 33-21-33 | GD02040 | | S.. | E | | | | D03184 | | 5 | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 57

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | |
| 138 | 20 | PA | | 3-0 | 33-21-33 | GD02204 | S.. | E | | D03102 | 5 | | | 050-099 | |
| 138 | 20 | PA | | 2-11 | 33-21-33 | GD02204 | S.. | E | | D03102 | 5 | | | 150-157, 275-278 | |
| 138 | 20 | PA | | 2-6 | 33-21-33 | GD02204 | S.. | E | | D03102 | 5 | | | 280-299 | |
| 139 | 20 | PA | | 4-0 | 33-21-33 | GD02052 | S.. | E | | D03114 | 5 | | | 050-099 | |
| 139 | 20 | PA | | 3-0 | 33-21-33 | GD02052 | S.. | E | | D03114 | 5 | | | 150-199, 275-278 | |
| 139 | 20 | PA | | 2-10 | 33-21-33 | GD02052 | S.. | E | | D03114 | 5 | | | 280-299 | |
| 140 | 20 | PA | | 4-0 | 33-21-33 | GD02076 | S.. | E | | D03082 | 5 | | | 050-099 | |
| 140 | 20 | PA | | 3-2 | 33-21-33 | GD02076 | S.. | E | | D03082 | 5 | | | 150-199, 275-278 | |
| 140 | 20 | PA | | 2-3 | 33-21-33 | GD02076 | S.. | E | | D03082 | 5 | | | 280-299 | |
| 141 | 20 | PA | | 4-0 | 33-21-33 | GD02048 | S.. | E | | D03192 | 5 | | | 050-099 | |
| 141 | 20 | PA | | 2-10 | 33-21-33 | GD04958 | S.. | E | | D03192 | 5 | | | 150-199, 275-278 | |
| 141 | 20 | PA | | 3-2 | 33-21-33 | GD04958 | S.. | E | | D03192 | 5 | | | 280-299 | |
| 142 | 20 | PA | | 4-0 | 33-21-33 | GD02212 | S.. | E | | D03110 | 5 | | | 050-099 | |
| 142 | 20 | PA | | 2-11 | 33-21-33 | GD02212 | S.. | E | | D03110 | 5 | | | 150-199, 275-278 | |
| 142 | 20 | PA | | 2-7 | 33-21-33 | GD02212 | S.. | E | | D03110 | 5 | | | 280-299 | |
| 143 | 20 | PA | | 15-0 | 33-24-11 | D05114P | | 19 | | SM00025 | | S | | 050-099 | |
| 143 | 20 | PA | | 13-10 | 33-24-11 | D05114P | | 1 | | SM00025 | | S | | 150-199, 275-278 | |
| 143 | 20 | PA | | 61-11 | 33-24-11 | D05114P | | 1 | | SM00025 | | S | | 280-299 | |
| 145 | 20 | PA | | 2-5 | 33-21-33 | GD02082 | S.. | E | | D03086 | 5 | | | 150-199 | |
| 146 | 20 | PA | | 4-0 | 33-21-33 | GD02056 | S.. | E | | D03118 | 5 | | | 150-199 | |
| 147 | 20 | PA | | 3-0 | 33-21-35 | GD02058 | S.. | E | | D03120 | 5 | | | 050-099 | |
| 147 | 20 | PA | | 2-10 | 33-21-35 | GD02058 | S.. | E | | D03120 | 5 | | | 150-199, 275-299 | |
| 148 | 20 | PA | | 3-0 | 33-21-35 | GD02060 | S.. | E | | D03122 | 5 | | | 050-099 | |
| 148 | 20 | PA | | 2-11 | 33-21-35 | GD02060 | S.. | E | | D03122 | 5 | | | 275-299 | |
| 149 | 20 | PA | | 3-2 | 33-21-35 | GD02062 | S.. | E | | D03124 | 5 | | | 275-299 | |
| 151 | 20 | PA | | 3-0 | 33-21-33 | GD02208 | S.. | E | | D03106 | 5 | | | 050-099 | |
| 151 | 20 | PA | | 2-8 | 33-21-33 | GD02208 | S.. | E | | D03106 | 5 | | | 150-199, 275-278 | |
| 151 | 20 | PA | | 2-6 | 33-21-33 | GD02208 | S.. | E | | D03106 | 5 | | | 280-299 | |
| 152 | 20 | PA | | 3-0 | 33-21-33 | D03188 | | 5 | | GD02044 | | S.. | E | 050-099 | |
| 152 | 20 | PA | | 2-8 | 33-21-33 | D03188 | | 5 | | GD02044 | | S.. | E | 150-199, 275-299 | |
| 153 | 22 | PA | | 12-0 | 33-21-33 | D03188 | | 3 | | SM00019 | | | 9 | 050-099 | |
| 153 | 22 | PA | | 9-6 | 33-21-33 | D03188 | | 3 | | SM00019 | | | 9 | 150-199 | |
| 153 | 22 | PA | | 11-1 | 33-21-33 | D03188 | | 3 | | SM00019 | | | 9 | 275-278 | |
| 153 | 22 | PA | | 9-3 | 33-21-33 | D03188 | | 3 | | SM00019 | | | 9 | 280-299 | |
| 154 | 22 | PA | | 12-0 | 33-21-33 | D03188 | | 4 | | SM00020 | | | 9 | 050-099 | |
| 154 | 22 | PA | | 9-6 | 33-21-33 | D03188 | | 4 | | SM00020 | | | 9 | 150-199 | |
| 154 | 22 | PA | | 11-1 | 33-21-33 | D03188 | | 4 | | SM00020 | | | 9 | 275-278 | |
| 154 | 22 | PA | | 9-3 | 33-21-33 | D03188 | | 4 | | SM00020 | | | 9 | 280-299 | |
| 171 | 22 | PA | | 15-0 | 33-21-33 | D03188 | | 1 | | D02950 | | | 9 | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 58

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 171 | 22 | | PA | 13-7 | 33-21-33 | D03188 | | 1 | | | | | D02950 | 9 | | | 150-199, 275-278 |
| 171 | 22 | | PA | 13-9 | 33-21-33 | D03188 | | 1 | | | | | D02950 | 9 | | | 280-299 |
| 172 | 22 | | PA | 15-0 | 33-21-33 | D03188 | | 2 | | | | | D02950 | 10 | | | 050-099 |
| 172 | 22 | | PA | 13-7 | 33-21-33 | D03188 | | 2 | | | | | D02950 | 10 | | | 150-199, 275-278 |
| 172 | 22 | | PA | 13-9 | 33-21-33 | D03188 | | 2 | | | | | D02950 | 10 | | | 280-299 |
| 173 | 22 | | PA | 4-0 | 33-21-33 | D02950 | | 11 | | | | | SM00019 | 9 | | | 050-099 |
| 173 | 22 | | PA | 4-7 | 33-21-33 | D02950 | | 11 | | | | | SM00019 | 9 | | | 150-199 |
| 173 | 22 | | PA | 3-0 | 33-21-33 | D02950 | | 11 | | | | | SM00019 | 9 | | | 275-278 |
| 173 | 22 | | PA | 5-0 | 33-21-33 | D02950 | | 11 | | | | | SM00019 | 9 | | | 280-299 |
| 174 | 22 | | PA | 4-0 | 33-21-33 | D02950 | | 12 | | | | | SM00020 | 9 | | | 050-099 |
| 174 | 22 | | PA | 4-7 | 33-21-33 | D02950 | | 12 | | | | | SM00020 | 9 | | | 150-199 |
| 174 | 22 | | PA | 3-0 | 33-21-33 | D02950 | | 12 | | | | | SM00020 | 9 | | | 275-278 |
| 174 | 22 | | PA | 5-0 | 33-21-33 | D02950 | | 12 | | | | | SM00020 | 9 | | | 280-299 |
| 175 | 20 | | PA | 28-11 | 33-26-21 | D00812 | | 13 | | | | | D05116P | 15 | | | 275-278 |
| 175 | 20 | | PA | 28-7 | 33-26-21 | D00812 | | 13 | | | | | D05116P | 15 | | | 280-299 |
| 176 | 20 | | PA | 9-9 | 33-26-21 | D10568 | | 13 | | | | | SM00044 | S | | | 275-278 |
| 176 | 20 | | PA | 1-7 | 33-26-21 | D10568 | | 13 | | | | | SM00044 | S | | | 280-299 |
| 177 | 20 | | PA | 6-2 | 33-26-21 | D00812 | | 10 | | | | | SM00044 | S | | | 275-278 |
| 177 | 20 | | PA | 13-11 | 33-26-21 | D00812 | | 10 | | | | | SM00044 | S | | | 280-299 |
| 178 | 20 | | PA | 40-0 | 33-24-11 | D00812 | | 12 | | | | | SM00025 | S | | | 050-099 |
| 178 | 20 | | PA | 40-6 | 33-24-11 | SP03578 | | 9 | | | | | SM00025 | S | | | 150-199 |
| 178 | 20 | | PA | 46-10 | 33-24-11 | D00812 | | 12 | | | | | SM00025 | S | | | 275-278 |
| 178 | 20 | | PA | 10-5 | 33-24-11 | D00812 | | 12 | | | | | SM00025 | S | | | 280-299 |
| 179 | 18 | | PA | 0-6 | 33-26-11 | D00812 | | 6 | | | | | SM00001 | 9 | | | 050-099, 275-299 |
| 179 | 18 | | PA | 4-7 | 33-26-11 | D00812 | | 6 | | | | | SM00001 | 9 | | | 150-199 |
| 181 | 22 | | PA | 10-0 | 33-26-11 | D00812 | | 15 | | | | | SM00027 | 9 | | | 050-099 |
| 181 | 22 | | PA | 53-9 | 33-26-11 | SP03908 | | 9 | | | | | D05114P | 22 | | | 150-199 |
| 181 | 22 | | PA | 37-10 | 33-26-11 | D00812 | | 15 | | | | | SM00027 | 9 | | | 275-278 |
| 181 | 22 | | PA | 58-4 | 33-26-11 | D00812 | | 15 | | | | | SM00027 | 9 | | | 280-299 |
| 182 | 20 | | PA | 10-0 | 33-26-11 | D00812 | | 17 | | | | | SM00026 | S | | | 050-099 |
| 182 | 20 | | PA | 46-4 | 33-26-11 | D00812 | | 17 | | | | | D05114P | 24 | | | 150-199 |
| 182 | 20 | | PA | 37-10 | 33-26-11 | D00812 | | 17 | | | | | SM00026 | S | | | 275-278 |
| 182 | 20 | | PA | 58-4 | 33-26-11 | D00812 | | 17 | | | | | SM00026 | S | | | 280-299 |
| 183 | 16 | | PA | 10-0 | 38-13-11 | D00812 | | 2 | | | | | GD03846 | A.. | E | | 050-099 |
| 183 | 16 | | PA | 9-4 | 38-13-11 | D00812 | | 2 | | | | | GD04976 | A.. | E | * | 150-199 |
| 183 | 16 | | PA | 3-5 | 38-13-11 | D00812 | | 2 | | | | | GD03846 | A.. | E | | 275-278 |
| 183 | 16 | | PA | 8-5 | 38-13-11 | D00812 | | 2 | | | | | GD03846 | A.. | E | | 280-299 |
| 184 | 20 | | PA | 10-0 | 33-26-11 | D00812 | | 1 | | | | | GD03846 | A.. | E | | 050-099 |
| 184 | 20 | | PA | 9-4 | 33-26-11 | D00812 | | 1 | | | | | GD04976 | A.. | E | * | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 59

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|--------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | | |
| 184 | 20 | | PA | 3-5 | 33-26-11 | D00812 | | | | | 1 | | | GD03846 | A.. | E | | 275-278 |
| 184 | 20 | | PA | 8-5 | 33-26-11 | D00812 | | | | | 1 | | | GD03846 | A.. | E | | 280-299 |
| 185 | 18 | | PA | 25-0 | 38-32-13 | D10570 | | | | | 20 | DK | | SM00046 | | S | | 050-099 |
| 185 | 20 | | PA | 3-5 | 38-32-13 | D00812 | | | | | 18 | | | GD03844 | D.. | E | | 275-276 |
| 185 | 20 | | PA | 3-5 | 38-32-16 | D00812 | | | | | 18 | | | GD03844 | D.. | E | | 277-278 |
| 185 | 20 | | PA | 8-5 | 38-32-16 | D00812 | | | | | 18 | | | GD03844 | D.. | E | | 280-299 |
| 186 | 20 | | PA | 3-5 | 38-32-13 | D00812 | | | | | 19 | | | GD03842 | S.. | E | | 275-276 |
| 186 | 20 | | PA | 3-5 | 38-32-16 | D00812 | | | | | 19 | | | GD03842 | S.. | E | | 277-278 |
| 186 | 20 | | PA | 8-5 | 38-32-16 | D00812 | | | | | 19 | | | GD03842 | S.. | E | | 280-299 |
| 187 | 18 | | PA | 18-5 | 38-32-13 | D00812 | | | | | 20 | DK | | SM00037 | | S | | 275-276 |
| 187 | 18 | | PA | 18-5 | 38-32-16 | D00812 | | | | | 20 | DK | | SM00037 | | S | | 277-278 |
| 187 | 18 | | PA | 0-7 | 38-32-16 | D00812 | | | | | 20 | DK | | SM00037 | | S | | 280-299 |
| 188 | 20 | | PA | 18-5 | 38-32-13 | D00812 | | | | | 21 | | | SM00036 | | S | | 275-276 |
| 188 | 20 | | PA | 18-5 | 38-32-16 | D00812 | | | | | 21 | | | SM00036 | | S | | 277-278 |
| 188 | 20 | | PA | 0-7 | 38-32-16 | D00812 | | | | | 21 | | | SM00036 | | S | | 280-299 |
| 189 | 22 | | PA | 23-0 | 33-25-11 | D10570 | | | | | 7 | | | SM00073 | | S | | 050-099 |
| 189 | 22 | | PA | 30-7 | 33-25-11 | D13414 | | | | | 7 | | | SP00329 | | S | | 150-199 |
| 189 | 22 | | PA | 10-8 | 33-25-11 | D00812 | | | | | 7 | | | SP00327 | | S | | 275-278 |
| 189 | 22 | | PA | 13-8 | 33-25-11 | D00812 | | | | | 7 | | | SP00327 | | S | | 280-299 |
| 18A | 20 | | PA | 11-1 | 33-26-21 | D10908 | | | | | 14 | | | D05114P | | 8 | | 280-299 |
| 190 | 22 | | PA | 2-0 | 33-25-11 | D10570 | | | | | 9 | | | SM00074 | | S | | 050-099 |
| 190 | 22 | | PA | 30-7 | 33-25-11 | D13414 | | | | | 9 | | | SP03694 | | 9 | | 150-199 |
| 190 | 22 | | PA | 6-2 | 33-25-11 | D00812 | | | | | 9 | | | SM00041 | | S | | 275-278 |
| 190 | 22 | | PA | 58-4 | 33-25-11 | D00812 | | | | | 9 | | | SM00041 | | S | | 280-299 |
| 191 | 22 | | PA | 20-0 | 33-25-11 | D10570 | | | | | 25 | | | D05116P | | 18 | | 050-099 |
| 191 | 22 | | PA | 30-7 | 33-25-11 | D13414 | | | | | 25 | | | SP00570 | | S | | 150-199 |
| 191 | 22 | | PA | 13-1 | 33-25-11 | D00812 | | | | | 25 | | | SP03214 | | S | | 275-278 |
| 191 | 22 | | PA | 13-2 | 33-25-11 | D00812 | | | | | 25 | | | SP03214 | | S | | 280-299 |
| 192 | 20 | | PA | 14-0 | 33-25-11 | D10570 | | | | | 26 | | | GD02506 | D.. | E | | 050-099 |
| 192 | 20 | | PA | 3-6 | 33-25-11 | D13414 | | | | | 26 | | | GD04990 | D.. | E | | 150-199 |
| 192 | 20 | | PA | 3-5 | 33-25-11 | D00812 | | | | | 26 | | | GD03844 | D.. | E | | 275-278 |
| 192 | 20 | | PA | 8-5 | 33-25-11 | D00812 | | | | | 26 | | | GD03844 | D.. | E | | 280-299 |
| 199 | 22 | | PA | 19-0 | 33-25-11 | SM00073 | | | | | | | S | D05116P | | 20 | | 050-099 |
| 201B | 22 | | PB | A | 29-0 | 23-31-14 | D00812 | | | | 5 | | | SP01694 | | S | | 050-099 |
| 201B | 22 | | PB | A | 15-1 | 23-31-14 | D00812 | | | | 5 | | | SP01694 | | S | | 150-199 |
| 201B | 22 | | PB | A | 10-8 | 23-31-14 | D00812 | | | | 5 | | | SP01694 | | S | | 275-278 |
| 201B | 22 | | PB | A | 6-0 | 23-31-14 | D00812 | | | | 5 | | | SM00068 | | S | | 280-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-14 | D00812 | | | | 16 | | | SP01692 | | S | | 050-099, 150-199, 275-278 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 60
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|----------|--------|-------------|---|------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 201R | 22 | PB | A | 0-0 | 23-31-14 | D00812 | | 16 | | | | | SM00067 | | S | | 280-299 |
| 204B | 22 | PB | AC | 16-11 | 23-31-14 | D10568 | | 5 | | | | | SP01694 | | S | | 275-278 |
| 204B | 22 | PB | AC | 9-11 | 23-31-14 | D10568 | | 5 | | | | | SM00068 | | S | | 280-299 |
| 204R | 22 | PB | AC | 0-0 | 23-31-14 | D10568 | | 16 | | | | | SP01692 | | S | | 275-278 |
| 204R | 22 | PB | AC | 0-0 | 23-31-14 | D10568 | | 16 | | | | | SM00067 | | S | | 280-299 |
| 205B | 22 | PB | IE | 9-0 | 23-31-14 | D10568 | | 5 | | | | | SP01694 | | S | | 050-099 |
| 205B | 22 | PB | IE | 26-6 | 23-31-14 | D10568 | | 5 | | | | | SP01694 | | S | | 150-199 |
| 205R | 22 | PB | IE | 0-0 | 23-31-14 | D10568 | | 16 | | | | | SP01692 | | S | | 050-099, 150-199 |
| 210B | 22 | PB | IJ | 43-0 | 23-31-14 | D10570 | | 5 | | | | | SP03592 | | S | | 050-099 |
| 210B | 22 | PB | IJ | 40-6 | 23-31-14 | D13414 | | 5 | | | | | SP03592 | | S | | 150-199 |
| 210R | 22 | PB | IJ | 0-0 | 23-31-14 | D10570 | | 5 | | | | | SP03590 | | S | | 050-099 |
| 210R | 22 | PB | IJ | 0-0 | 23-31-14 | D13414 | | 16 | | | | | SP03590 | | S | | 150-199 |
| 211B | 22 | PB | K | 10-11 | 23-31-14 | D10908 | | 5 | | | | | D05114P | 26 | | | 275-278 |
| 211B | 22 | PB | K | 11-1 | 23-31-14 | D10908 | | 5 | | | | | D05114P | 26 | | | 280-299 |
| 211R | 22 | PB | K | 0-0 | 23-31-14 | D10908 | | 16 | | | | | D05114P | 25 | | | 275-299 |
| 228B | 22 | PB | JC | 9-5 | 23-31-14 | SP01694 | | | S | | | | SM00068 | | S | | 280-299 |
| 228R | 22 | PB | JC | 0-0 | 23-31-14 | SP01692 | | | S | | | | SM00067 | | S | | 280-299 |
| 520 | 20 | PA | | 39-5 | 33-21-33 | D05114P | | 16 | | | | | D11220 | 5 | | | 150-154, 157-165, 167-199, 275-278 |
| 520 | 20 | PQ | S | 39-5 | 33-21-33 | D05114P | | 16 | | | | | D11220 | 5 | | | 155-156, 166 |
| 520 | 20 | PA | | 39-8 | 33-21-33 | D05114P | | 16 | | | | | D11220 | 5 | | | 280-299 |
| 520Z | | | S | 0-0 | 33-21-33 | D05114P | | | DED | | | | D11220 | DED | | | 155-156, 166 |
| 521 | 22 | PA | | 49-0 | 33-26-11 | SM00038 | | | 9 | | | | D05114P | 4 | | | 050-099 |
| 521 | 22 | PA | | 42-3 | 33-26-11 | SM00001 | | | 9 | | | | D05114P | 4 | | | 150-199 |
| 521 | 22 | PA | | 1-10 | 33-26-11 | SM00038 | | | 9 | | | | D05114P | 4 | | | 275-278 |
| 521 | 22 | PA | | 1-2 | 33-26-11 | SM00038 | | | 9 | | | | D05114P | 4 | | | 280-299 |
| 522 | 22 | PA | | 44-0 | 33-22-21 | D05114P | | 36 | | | | | STA0654L | CAP | Y | | 280-299 |
| 523 | 20 | PA | | 31-9 | 33-26-21 | L00807 | | | S | C | | | D05114P | 31 | | | 280-299 |
| 524 | 20 | PA | | 12-3 | 33-26-21 | L00807 | | | P | C | | | SM00065 | | | 9 | 280-299 |
| 525 | 20 | PA | | 4-7 | 33-26-21 | L00807 | | | G | C | | | GD01924 | A.. | 2 | | 280-299 |
| 546 | 16 | PA | | 46-0 | 33-21-33 | D05114P | | 15 | | | | | D11222 | 5 | FM | | 275-278 |
| 546 | 16 | PA | | 46-9 | 33-21-33 | D05114P | | 15 | | | | | D11222 | 5 | FM | | 280-299 |
| 547 | 16 | PA | | 3-9 | 33-21-33 | D11222 | | 7 | FM | | | | GD04976 | A.. | E | | 275-278 |
| 547 | 16 | PA | | 8-0 | 33-21-33 | D11222 | | 7 | FM | | | | GD04976 | A.. | E | | 280-299 |
| 548 | 16 | PA | | 3-9 | 33-21-33 | D11222 | | 8 | FM | | | | GD04824 | S.. | E | | 275-278 |
| 548 | 16 | PA | | 8-0 | 33-21-33 | D11222 | | 8 | FM | | | | GD04824 | S.. | E | | 280-299 |
| 549 | 22 | PA | | 21-0 | 33-21-33 | D11222 | | 2 | | | | | D11228 | 1 | | | 275-278 |
| 549 | 22 | PA | | 22-2 | 33-21-33 | D11222 | | 2 | | | | | D11228 | 1 | | | 280-299 |
| 550 | 22 | PA | | 21-0 | 33-21-33 | D11222 | | 3 | | | | | D11228 | 2 | | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 61

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | | |
| 550 | 22 | PA | | | 22-2 | 33-21-33 | D11222 | | 3 | | | | D11228 | | 2 | | | 280-299 |
| 551 | 22 | PA | | | 17-4 | 33-21-33 | D11228 | | 3 | | | | SM00029 | | 9 | | | 275-278 |
| 551 | 22 | PA | | | 17-10 | 33-21-33 | D11228 | | 3 | | | | SM00029 | | 9 | | | 280-299 |
| 552 | 22 | PA | | | 17-4 | 33-21-33 | D11228 | | 4 | | | | SM00030 | | 9 | | | 275-278 |
| 552 | 22 | PA | | | 17-10 | 33-21-33 | D11228 | | 4 | | | | SM00030 | | 9 | | | 280-299 |
| 553 | 20 | PA | | | 3-1 | 33-21-33 | D11228 | | 5 | | | | GD04980 | S.. | E | | | 275-278 |
| 553 | 20 | PA | | | 2-5 | 33-21-33 | D11228 | | 5 | | | | GD04980 | S.. | E | | | 280-299 |
| 554 | 22 | PA | | | 7-7 | 33-21-33 | D11230 | | 3 | | | | SM00029 | | 9 | | | 275-278 |
| 554 | 22 | PA | | | 6-8 | 33-21-33 | D11230 | | 3 | | | | SM00029 | | 9 | | | 280-299 |
| 555 | 22 | PA | | | 7-7 | 33-21-33 | D11230 | | 4 | | | | SM00030 | | 9 | | | 275-278 |
| 555 | 22 | PA | | | 6-8 | 33-21-33 | D11230 | | 4 | | | | SM00030 | | 9 | | | 280-299 |
| 556 | 22 | PA | | | 7-11 | 33-21-33 | D11222 | | 9 | | | | D11230 | | 1 | | | 275-278 |
| 556 | 22 | PA | | | 6-10 | 33-21-33 | D11222 | | 9 | | | | D11230 | | 1 | | | 280-299 |
| 557 | 22 | PA | | | 7-11 | 33-21-33 | D11222 | | 10 | | | | D11230 | | 2 | | | 275-278 |
| 557 | 22 | PA | | | 6-10 | 33-21-33 | D11222 | | 10 | | | | D11230 | | 2 | | | 280-299 |
| 558 | 20 | PA | | | 2-10 | 33-21-33 | D11230 | | 5 | | | | GD02048 | S.. | E | | | 275-278 |
| 558 | 20 | PA | | | 2-5 | 33-21-33 | D11230 | | 5 | | | | GD02048 | S.. | E | | | 280-299 |
| 559 | 22 | PA | | | 4-3 | 33-21-33 | D11222 | | 11 | | | | SM00029 | | 9 | | | 275-278 |
| 559 | 22 | PA | | | 4-11 | 33-21-33 | D11222 | | 11 | | | | SM00029 | | 9 | | | 280-299 |
| 560 | 22 | PA | | | 4-3 | 33-21-33 | D11222 | | 12 | | | | SM00030 | | 9 | | | 275-278 |
| 560 | 22 | PA | | | 4-11 | 33-21-33 | D11222 | | 12 | | | | SM00030 | | 9 | | | 280-299 |
| 568 | 16 | PA | | | 49-0 | 38-13-11 | D05114P | | 23 | FL | | | SM00034 | | 9 | | | 050-099 |
| 568 | 16 | PA | | | 22-11 | 38-13-11 | D05114P | | 41 | | | | SM00034 | | 9 | | | 275-278 |
| 568 | 16 | PA | | | 3-11 | 38-13-11 | D05114P | | 41 | | | | SM00034 | | 9 | | | 280-299 |
| 576 | 20 | PA | | | 59-0 | 33-24-11 | SM00025 | | | S | | | D05116P | | 10 | | | 050-099 |
| 576 | 20 | PA | | | 67-8 | 33-24-11 | SM00025 | | | S | | | D05116P | | 10 | | | 150-199, 275-278 |
| 576 | 20 | PA | | | 19-2 | 33-24-11 | SM00025 | | | S | | | D05116P | | 10 | | | 280-299 |
| 577 | 20 | PA | | | 26-6 | 33-24-11 | SP01586 | | | 9 | | | D10568 | | 12 | | | 150-199 |
| 582 | 20 | PA | | | 45-0 | 33-26-11 | D05114P | | 24 | | | | SM00026 | | | S | | 050-099 |
| 582 | 20 | PA | | | 22-11 | 33-26-11 | SM00026 | | | S | | | D05114P | | 24 | | | 275-278 |
| 582 | 20 | PA | | | 3-11 | 33-26-11 | SM00026 | | | S | | | D05114P | | 24 | | | 280-299 |
| 583 | 20 | PA | | | 45-0 | 33-26-11 | D05114P | | 22 | | | | SM00027 | | | 9 | | 050-099 |
| 583 | 20 | PA | | | 22-11 | 33-26-11 | SM00027 | | | 9 | | | D05114P | | 22 | | | 275-278 |
| 583 | 20 | PA | | | 3-11 | 33-26-11 | SM00027 | | | 9 | | | D05114P | | 22 | | | 280-299 |
| 584 | 22 | PA | | | 49-0 | 33-26-11 | D05114P | | 3 | | | | SM00035 | | | 9 | | 050-099 |
| 584 | 22 | PA | | | 10-6 | 33-26-11 | SM00035 | | | 9 | | | D05114P | | 3 | | | 275-278 |
| 584 | 22 | PA | | | 0-7 | 33-26-11 | SM00035 | | | 9 | | | D05114P | | 3 | | | 280-299 |
| 589 | 20 | PA | | | 23-1 | 33-26-21 | D05114P | | 6 | | | | SM00065 | | | 9 | | 280-299 |
| 590 | 20 | PA | | | 2-0 | 33-26-21 | D13490 | | 12 | | | | SM00077 | | | S | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 62

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 591 | 20 | | PA | 3-10 | 33-21-33 | D11220 | | 7 | | | | | GD04968 | A.. | E | | 150-154, 157-165, 167-199, 275-278 |
| 591 | 20 | | PQ | XP | 3-10 | 33-21-33 | D11220 | | 7 | | | | GD04968 | A.. | E | | 155-156, 166 |
| 591 | 20 | | PA | | 3-4 | 33-21-33 | D11220 | | 7 | | | | GD04968 | A.. | E | | 280-299 |
| 591Z | | | | XP | 0-0 | 33-21-33 | D11220 | | DED | | | | GD04968 | DED | | | 155-156, 166 |
| 592 | 20 | | PA | | 3-10 | 33-21-33 | D11220 | | 8 | | | | GD04846 | S.. | E | | 150-199, 275-278 |
| 592 | 20 | | PA | | 3-4 | 33-21-33 | D11220 | | 8 | | | | GD04846 | S.. | E | | 280-299 |
| 593 | 22 | | PA | | 22-0 | 33-21-33 | D11220 | | 2 | | | | D11224 | 1 | | | 150-199, 275-278 |
| 593 | 22 | | PA | | 22-4 | 33-21-33 | D11220 | | 2 | | | | D11224 | 1 | | | 280-299 |
| 594 | 22 | | PA | | 22-0 | 33-21-33 | D11220 | | 3 | | | | D11224 | 2 | | | 150-199, 275-278 |
| 594 | 22 | | PA | | 22-4 | 33-21-33 | D11220 | | 3 | | | | D11224 | 2 | | | 280-299 |
| 595 | 22 | | PA | | 18-5 | 33-21-33 | SM00031 | | 9 | | | | D11224 | 3 | | | 150-199, 275-278 |
| 595 | 22 | | PA | | 18-6 | 33-21-33 | SM00031 | | 9 | | | | D11224 | 3 | | | 280-299 |
| 596 | 22 | | PA | | 18-5 | 33-21-33 | SM00032 | | 9 | | | | D11224 | 4 | | | 150-199, 275-278 |
| 596 | 22 | | PA | | 18-6 | 33-21-33 | SM00032 | | 9 | | | | D11224 | 4 | | | 280-299 |
| 597 | 20 | | PA | | 3-1 | 33-21-33 | D11224 | | 5 | | | | GD04972 | S.. | E | | 150-199, 275-278 |
| 597 | 20 | | PA | | 2-10 | 33-21-33 | D11224 | | 5 | | | | GD04972 | S.. | E | | 280-299 |
| 598 | 22 | | PA | | 7-3 | 33-21-33 | SM00031 | | 9 | | | | D11226 | 3 | | | 150-199, 275-278 |
| 598 | 22 | | PA | | 6-9 | 33-21-33 | SM00031 | | 9 | | | | D11226 | 3 | | | 280-299 |
| 599 | 22 | | PA | | 7-3 | 33-21-33 | SM00032 | | 9 | | | | D11226 | 4 | | | 150-199, 275-278 |
| 599 | 22 | | PA | | 6-9 | 33-21-33 | SM00032 | | 9 | | | | D11226 | 4 | | | 280-299 |
| 600 | 22 | | PA | | 7-5 | 33-21-33 | D11220 | | 9 | | | | D11226 | 1 | | | 150-199, 275-278 |
| 600 | 22 | | PA | | 6-4 | 33-21-33 | D11220 | | 9 | | | | D11226 | 1 | | | 280-299 |
| 601 | 22 | | PA | | 7-5 | 33-21-33 | D11220 | | 10 | | | | D11226 | 2 | | | 150-199, 275-278 |
| 601 | 22 | | PA | | 6-4 | 33-21-33 | D11220 | | 10 | | | | D11226 | 2 | | | 280-299 |
| 602 | 20 | | PA | | 2-11 | 33-21-33 | D11226 | | 5 | | | | GD04974 | S.. | E | | 150-199, 275-278 |
| 602 | 20 | | PA | | 2-7 | 33-21-33 | D11226 | | 5 | | | | GD04974 | S.. | E | | 280-299 |
| 603 | 22 | | PA | | 4-2 | 33-21-33 | SM00031 | | 9 | | | | D11220 | 11 | | | 150-199, 275-278 |
| 603 | 22 | | PA | | 4-5 | 33-21-33 | SM00031 | | 9 | | | | D11220 | 11 | | | 280-299 |
| 604 | 22 | | PA | | 4-2 | 33-21-33 | SM00032 | | 9 | | | | D11220 | 12 | | | 150-199, 275-278 |
| 604 | 22 | | PA | | 4-5 | 33-21-33 | SM00032 | | 9 | | | | D11220 | 12 | | | 280-299 |
| 605 | 20 | | PA | | 2-9 | 33-21-35 | GD04632 | | S.. | E | | | D11242 | 5 | | | 150-199, 275-299 |
| 606 | 22 | | PA | | 10-11 | 33-21-35 | D02010 | | 9 | | | | D11242 | 1 | | | 150-199 |
| 606 | 22 | | PA | | 15-5 | 33-21-35 | D02010 | | 9 | | | | D11242 | 1 | | | 275-278 |
| 606 | 22 | | PA | | 15-9 | 33-21-35 | D02010 | | 9 | | | | D11242 | 1 | | | 280-299 |
| 607 | 22 | | PA | | 10-11 | 33-21-35 | D02010 | | 10 | | | | D11242 | 2 | | | 150-199 |
| 607 | 22 | | PA | | 15-5 | 33-21-35 | D02010 | | 10 | | | | D11242 | 2 | | | 275-278 |
| 607 | 22 | | PA | | 15-9 | 33-21-35 | D02010 | | 10 | | | | D11242 | 2 | | | 280-299 |
| 608 | 22 | | PA | | 7-6 | 33-21-35 | SM00005 | | 9 | | | | D11242 | 4 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 63

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|-----|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | | |
| 609 | 22 | | PA | 7-6 | 33-21-35 | SM00004 | | | | 9 | | | | D11242 | 3 | | | 150-199, 275-299 |
| 611 | 20 | | PA | 11-0 | 33-26-11 | D10568 | | | 1 | | | | | GD04444 | A.. | 2 | | 050-099 |
| 611 | 20 | | PA | 12-1 | 33-26-11 | D10908 | | | 1 | | | | | GD01662 | A.. | 2 | | 275-278 |
| 611 | 20 | | PA | 12-3 | 33-26-11 | D10908 | | | 1 | | | | | GD01662 | A.. | 2 | | 280-299 |
| 612 | 16 | | PA | 14-0 | 38-13-11 | D10570 | | | 2 | | | | | GD01464 | A.. | E | | 050-099 |
| 612 | 16 | | PA | 12-1 | 38-13-11 | D10908 | | | 2 | | | | | GD01662 | A.. | 2 | | 275-278 |
| 612 | 16 | | PA | 12-3 | 38-13-11 | D10908 | | | 2 | | | | | GD01662 | A.. | 2 | | 280-299 |
| 616 | 18 | | PA | 20-0 | 33-26-11 | SM00035 | | | | 9 | | | | D10568 | | 6 | | 050-099 |
| 616 | 18 | | PA | 0-11 | 33-26-11 | D10908 | | | 6 | | | | | SM00035 | | 9 | | 275-278 |
| 616 | 18 | | PA | 11-1 | 33-26-11 | D10908 | | | 6 | | | | | SM00035 | | 9 | | 280-299 |
| 617 | 22 | | PA | 10-11 | 33-25-11 | D10908 | | | 7 | | | | | D05114P | | 7 | | 275-278 |
| 617 | 22 | | PA | 11-1 | 33-25-11 | D10908 | | | 7 | | | | | D05114P | | 7 | | 280-299 |
| 618 | 16 | | PA | 25-0 | 38-13-11 | D10570 | | | 8 | | | | | SM00034 | | 9 | | 050-099 |
| 618 | 16 | | PA | 30-10 | 38-13-11 | D10908 | | | 8 | | | | | SM00034 | | 9 | | 275-278 |
| 618 | 16 | | PA | 12-7 | 38-13-11 | D10908 | | | 8 | | | | | SM00034 | | 9 | | 280-299 |
| 619 | 22 | | PA | 65-8 | 33-25-11 | D10908 | | | 9 | | | | | SM00041 | | S | | 275-278 |
| 619 | 22 | | PA | 12-7 | 33-25-11 | D10908 | | | 9 | | | | | SM00041 | | S | | 280-299 |
| 620 | 20 | | PA | 24-0 | 33-26-21 | D00812 | | | 13 | | | | | D10568 | | 10 | | 050-099 |
| 620 | 20 | | PA | 19-7 | 33-26-21 | D10568 | | | 10 | | | | | D00812 | | 13 | | 150-199 |
| 620 | 20 | | PA | 10-11 | 33-26-21 | D10908 | | | 10 | | | | | D05114P | | 10 | | 275-278 |
| 620 | 20 | | PA | 11-1 | 33-26-21 | D10908 | | | 10 | | | | | D05114P | | 10 | | 280-299 |
| 622 | 20 | | PA | 21-9 | 33-24-11 | D10908 | | | 12 | | | | | SM00025 | | S | | 275-278 |
| 622 | 20 | | PA | 70-1 | 33-24-11 | D10908 | | | 12 | | | | | SM00025 | | S | | 280-299 |
| 623 | 20 | | PA | 2-0 | 33-26-21 | D10568 | | | 13 | | | | | SM00072 | | 9 | | 050-099 |
| 623 | 20 | | PA | 26-6 | 33-26-21 | D10568 | | | 13 | | | | | SP03704 | | 9 | | 150-199 |
| 623 | 20 | | PA | 10-11 | 33-26-21 | D10908 | | | 13 | | | | | D05114P | | 28 | | 275-278 |
| 623 | 20 | | PA | 11-1 | 33-26-21 | D10908 | | | 13 | | | | | D05114P | | 28 | | 280-299 |
| 625 | 22 | | PA | 16-0 | 33-26-11 | SM00027 | | | | 9 | | | | D10568 | | 15 | | 050-099 |
| 625 | 22 | | PA | 30-10 | 33-26-11 | D10908 | | | 15 | | | | | SM00027 | | 9 | | 275-278 |
| 625 | 22 | | PA | 12-7 | 33-26-11 | D10908 | | | 15 | | | | | SM00027 | | 9 | | 280-299 |
| 627 | 20 | | PA | 16-0 | 33-26-11 | SM00026 | | | | S | | | | D10568 | | 17 | | 050-099 |
| 627 | 20 | | PA | 30-10 | 33-26-11 | D10908 | | | 17 | | | | | SM00026 | | S | | 275-278 |
| 627 | 20 | | PA | 12-7 | 33-26-11 | D10908 | | | 17 | | | | | SM00026 | | S | | 280-299 |
| 628 | 20 | | PA | 12-1 | 38-32-13 | D10908 | | | 18 | | | | | GD01662 | | D.. | 2 | 275-276 |
| 628 | 20 | | PA | 12-1 | 38-32-16 | D10908 | | | 18 | | | | | GD01662 | | D.. | 2 | 277-278 |
| 628 | 20 | | PA | 12-3 | 38-32-16 | D10908 | | | 18 | | | | | GD01662 | | D.. | 2 | 280-299 |
| 629 | 20 | | PA | 12-1 | 38-32-13 | D10908 | | | 19 | | | | | GD01662 | | S.. | 2 | 275-276 |
| 629 | 20 | | PA | 12-1 | 38-32-16 | D10908 | | | 19 | | | | | GD01662 | | S.. | 2 | 277-278 |
| 629 | 20 | | PA | 12-3 | 38-32-16 | D10908 | | | 19 | | | | | GD01662 | | S.. | 2 | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 64

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 630 | 18 | | PA | 88-5 | 38-32-13 | D10908 | | 20 | DK | | | | D05116P | 8 | | | 275-276 |
| 630 | 18 | | PA | 88-5 | 38-32-16 | D10908 | | 20 | DK | | | | D05116P | 8 | | | 277-278 |
| 630 | 18 | | PA | 88-2 | 38-32-16 | D10908 | | 20 | DK | | | | D05116P | 8 | | | 280-299 |
| 631 | 22 | | PA | 88-5 | 38-32-13 | D10908 | | 21 | | | | | D05116P | 18 | | | 275-276 |
| 631 | 22 | | PA | 88-5 | 38-32-16 | D10908 | | 21 | | | | | D05116P | 18 | | | 277-278 |
| 631 | 22 | | PA | 88-2 | 38-32-16 | D10908 | | 21 | | | | | D05116P | 18 | | | 280-299 |
| 635 | 22 | | PA | 17-0 | 33-25-11 | D10908 | | 25 | | | | | SP00568 | | S | | 275-278 |
| 635 | 22 | | PA | 17-2 | 33-25-11 | D10908 | | 25 | | | | | SP00568 | | S | | 280-299 |
| 636 | 20 | | PA | 12-1 | 33-25-11 | D10908 | | 26 | | | | | GD01662 | D.. | 2 | | 275-278 |
| 636 | 20 | | PA | 12-3 | 33-25-11 | D10908 | | 26 | | | | | GD01662 | D.. | 2 | | 280-299 |
| 641 | 20 | | PA | 14-0 | 33-26-11 | D10570 | | 1 | | | | | GD01464 | A.. | E | | 050-099 |
| 641 | 20 | | PA | 6-2 | 33-26-11 | D10568 | | 1 | | | | | GD00934 | A.. | 2 | | 275-299 |
| 642 | 16 | | PA | 11-0 | 38-13-11 | D10568 | | 2 | | | | | GD04444 | A.. | 2 | | 050-099 |
| 642 | 16 | | PA | 6-2 | 38-13-11 | D10568 | | 2 | | | | | GD00934 | A.. | 2 | | 275-299 |
| 644 | 20 | | PA | 9-9 | 33-26-21 | D10568 | | 14 | | | | | SM00044 | | S | | 275-278 |
| 644 | 20 | | PA | 1-7 | 33-26-21 | D10568 | | 14 | | | | | SM00044 | | S | | 280-299 |
| 645 | 20 | | PA | 66-5 | 33-26-21 | D10568 | | 10 | | | | | D05114P | 6 | | | 275-278 |
| 645 | 20 | | PA | 43-10 | 33-26-21 | D10568 | | 10 | | | | | SM00065 | | 9 | | 280-299 |
| 646 | 18 | | PA | 2-0 | 33-26-11 | D10570 | | 6 | | | | | SM00039 | | 9 | | 050-099 |
| 646 | 18 | | PA | 9-9 | 33-26-11 | D10568 | | 6 | | | | | SM00039 | | 9 | | 275-278 |
| 646 | 18 | | PA | 1-7 | 33-26-11 | D10568 | | 6 | | | | | SM00039 | | 9 | | 280-299 |
| 647 | 22 | | PA | 16-11 | 33-25-11 | D10568 | | 7 | | | | | SP00329 | | S | | 275-278 |
| 647 | 22 | | PA | 18-4 | 33-25-11 | D10568 | | 7 | | | | | SP00329 | | S | | 280-299 |
| 648 | 16 | | PA | 20-0 | 38-13-11 | D10568 | | 8 | | | | | SM00034 | | 9 | | 050-099 |
| 648 | 16 | | PA | 44-1 | 38-13-11 | D10568 | | 8 | | | | | SM00034 | | 9 | | 275-278 |
| 648 | 16 | | PA | 63-0 | 38-13-11 | D10568 | | 8 | | | | | SM00034 | | 9 | | 280-299 |
| 649 | 22 | | PA | 9-9 | 33-25-11 | D10568 | | 9 | | | | | SM00041 | | S | | 275-278 |
| 649 | 22 | | PA | 63-0 | 33-25-11 | D10568 | | 9 | | | | | SM00041 | | S | | 280-299 |
| 652 | 20 | | PA | 40-0 | 33-24-11 | D10568 | | 12 | | | | | SM00025 | | S | | 050-099 |
| 652 | 20 | | PA | 53-7 | 33-24-11 | D10568 | | 12 | | | | | SM00025 | | S | | 275-278 |
| 652 | 20 | | PA | 11-8 | 33-24-11 | D10568 | | 12 | | | | | SM00025 | | S | | 280-299 |
| 655 | 22 | | PA | 29-0 | 33-26-11 | D10570 | | 15 | | | | | SM00027 | | 9 | | 050-099 |
| 655 | 22 | | PA | 44-1 | 33-26-11 | D10568 | | 15 | | | | | SM00027 | | 9 | | 275-278 |
| 655 | 22 | | PA | 63-0 | 33-26-11 | D10568 | | 15 | | | | | SM00027 | | 9 | | 280-299 |
| 657 | 20 | | PA | 29-0 | 33-26-11 | D10570 | | 17 | | | | | SM00026 | | S | | 050-099 |
| 657 | 20 | | PA | 44-1 | 33-26-11 | D10568 | | 17 | | | | | SM00026 | | S | | 275-278 |
| 657 | 20 | | PA | 63-0 | 33-26-11 | D10568 | | 17 | | | | | SM00026 | | S | | 280-299 |
| 658 | 20 | | PA | 6-2 | 38-32-13 | D10568 | | 18 | | | | | GD00934 | D.. | 2 | | 275-276 |
| 658 | 20 | | PA | 6-2 | 38-32-16 | D10568 | | 18 | | | | | GD00934 | D.. | 2 | | 277-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 65

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 659 | 20 | | PA | 6-2 | 38-32-13 | D10568 | | 19 | | | | | GD00934 | S.. | 2 | | 275-276 |
| 659 | 20 | | PA | 6-2 | 38-32-16 | D10568 | | 19 | | | | | GD00934 | S.. | 2 | | 277-299 |
| 660 | 18 | | PA | 24-8 | 38-32-13 | D10568 | | 20 | DK | | | | SM00037 | | S | | 275-276 |
| 660 | 18 | | PA | 24-8 | 38-32-16 | D10568 | | 20 | DK | | | | SM00037 | | S | | 277-278 |
| 660 | 18 | | PA | 14-11 | 38-32-16 | D10568 | | 20 | DK | | | | SM00037 | | S | | 280-299 |
| 661 | 22 | | PA | 24-8 | 38-32-13 | D10568 | | 21 | | | | | SM00036 | | S | | 275-276 |
| 661 | 22 | | PA | 24-8 | 38-32-16 | D10568 | | 21 | | | | | SM00036 | | S | | 277-278 |
| 661 | 22 | | PA | 14-11 | 38-32-16 | D10568 | | 21 | | | | | SM00036 | | S | | 280-299 |
| 665 | 22 | | PA | 14-5 | 33-25-11 | D10568 | | 25 | | | | | SP00570 | | S | | 275-299 |
| 666 | 22 | | PA | 25-0 | 38-32-13 | D10570 | | 21 | | | | | SM00047 | | S | | 050-099 |
| 666 | 20 | | PA | 6-2 | 33-25-11 | D10568 | | 26 | | | | | GD00934 | D.. | 2 | | 275-299 |
| 667 | 20 | | PA | 14-0 | 38-32-13 | D10570 | | 18 | | | | | GD02506 | D.. | E | | 050-099 |
| 668 | 20 | | PA | 14-0 | 38-32-13 | D10570 | | 19 | | | | | GD01466 | S.. | E | | 050-099 |
| 669 | 20 | | PA | 26-0 | 25-42-11 | D13490 | | 10 | | | | | SM00045 | | 9 | | 050-099 |
| 669 | 20 | | PA | 29-11 | 25-42-11 | D13486 | | 10 | | | | | SM00045 | | 9 | | 150-199 |
| 670 | 20 | | PA | 10-0 | 38-32-13 | D00812 | | 18 | | | | | GD03844 | D.. | E | | 050-099 |
| 670 | 20 | | PA | 2-6 | 38-32-13 | D00812 | | 18 | | | | | GD04978 | D.. | E | | 150-156, 162-165 |
| 670 | 20 | | PA | 2-6 | 38-32-16 | D00812 | | 18 | | | | | GD04978 | D.. | E | | 157, 166-199 |
| 671 | 22 | | PA | 26-3 | 33-21-33 | D02110 | | 9 | | | | | D03098 | | 1 | | 275-278 |
| 671 | 22 | | PA | 26-5 | 33-21-33 | D02110 | | 9 | | | | | D03098 | | 1 | | 280-299 |
| 672 | 22 | | PA | 26-3 | 33-21-33 | D02110 | | 10 | | | | | D03098 | | 2 | | 275-278 |
| 672 | 22 | | PA | 26-5 | 33-21-33 | D02110 | | 10 | | | | | D03098 | | 2 | | 280-299 |
| 673 | 22 | | PA | 23-9 | 33-21-33 | SM00011 | | | 9 | | | | D03098 | | 3 | | 275-278 |
| 673 | 22 | | PA | 22-8 | 33-21-33 | SM00011 | | | 9 | | | | D03098 | | 3 | | 280-299 |
| 674 | 22 | | PA | 23-9 | 33-21-33 | SM00012 | | | 9 | | | | D03098 | | 4 | | 275-278 |
| 674 | 22 | | PA | 22-8 | 33-21-33 | SM00012 | | | 9 | | | | D03098 | | 4 | | 280-299 |
| 675 | 20 | | PA | 7-5 | 33-21-33 | GD04736 | | S.. | E | | | | D03098 | | 5 | | 275-278 |
| 675 | 20 | | PA | 7-7 | 33-21-33 | GD04736 | | S.. | E | | | | D03098 | | 5 | | 280-299 |
| 676 | 20 | | PA | 10-0 | 38-32-13 | D00812 | | 19 | | | | | GD03842 | S.. | E | | 050-099 |
| 676 | 20 | | PA | 2-6 | 38-32-13 | D00812 | | 19 | | | | | GD04978 | S.. | E | | 150-154 |
| 676 | 20 | | PA | 9-4 | 38-32-13 | D00812 | | 19 | | | | | GD04824 | S.. | E | | 155-156, 162-165 |
| 676 | 20 | | PA | 9-4 | 38-32-16 | D00812 | | 19 | | | | | GD04824 | S.. | E | | 157, 166-199 |
| 677 | 18 | | PA | 5-0 | 38-32-13 | D00812 | | 20 | DK | | | | SM00046 | | S | | 050-099 |
| 677 | 18 | | PA | 4-7 | 38-32-13 | D00812 | | 20 | DK | | | | SM00046 | | S | | 150-156, 162-165 |
| 677 | 18 | | PA | 4-7 | 38-32-16 | D00812 | | 20 | DK | | | | SM00046 | | S | | 157, 166-199 |
| 678 | 22 | | PA | 6-0 | 38-32-13 | D00812 | | 21 | | | | | SM00047 | | S | | 050-099 |
| 678 | 22 | | PA | 4-7 | 38-32-13 | D00812 | | 21 | | | | | SM00047 | | S | | 150-156, 162-165 |
| 678 | 22 | | PA | 4-7 | 38-32-16 | D00812 | | 21 | | | | | SM00047 | | S | | 157, 166-199 |
| 679 | 20 | | PA | 12-0 | 38-32-13 | SM00046 | | | S | | | | SP03816 | | S | | 150-156, 162-165 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 66

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|--|-----|----|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | | | | |
| 679 | 20 | | PA | 12-0 | 38-32-16 | SM00046 | | | | | | | | S | SP03816 | | | | S | 157, 166-199 |
| 680 | 22 | | PA | 24-0 | 33-26-11 | SM00038 | | | | | | | | 9 | SM00039 | | | | 9 | 050-099 |
| 680 | 22 | | PA | 56-5 | 33-26-11 | SM00039 | | | | | | | | 9 | SM00038 | | | | 9 | 275-278 |
| 680 | 22 | | PA | 64-9 | 33-26-11 | SM00039 | | | | | | | | 9 | SM00038 | | | | 9 | 280-299 |
| 681 | 22 | | PA | 4-0 | 33-26-11 | SM00038 | | | | | | | | 9 | SM00001 | | | | 9 | 050-099 |
| 681 | 22 | | PA | 58-10 | 33-26-11 | SM00038 | | | | | | | | 9 | SM00001 | | | | 9 | 275-278 |
| 681 | 22 | | PA | 61-1 | 33-26-11 | SM00038 | | | | | | | | 9 | SM00001 | | | | 9 | 280-299 |
| 682 | 20 | | PA | 12-0 | 38-32-13 | SM00047 | | | | | | | | S | SP03814 | | | | S | 150-156, 162-165 |
| 682 | 20 | | PA | 12-0 | 38-32-16 | SM00047 | | | | | | | | S | SP03814 | | | | S | 157, 166-199 |
| 683 | 20 | | PA | 11-0 | 38-32-13 | D10568 | | | 18 | | | | | | GD04444 | | D.. | 2 | | 050-099 |
| 683 | 20 | | PA | 4-8 | 38-32-13 | D10568 | | | 18 | | | | | | GD04874 | | D.. | 2 | | 150-156, 162-165 |
| 683 | 20 | | PA | 4-8 | 38-32-16 | D10568 | | | 18 | | | | | | GD04874 | | D.. | 2 | | 157, 166-199 |
| 684 | 18 | | PA | 20-0 | 38-32-13 | D10568 | | | 20 | DK | | | | | SM00046 | | | | S | 050-099 |
| 684 | 20 | | PA | 15-6 | 38-32-13 | D10568 | | | 20 | | | | | | SM00046 | | | | S | 150-156, 162-165 |
| 684 | 20 | | PA | 15-6 | 38-32-16 | D10568 | | | 20 | | | | | | SM00046 | | | | S | 157, 166-199 |
| 685 | 22 | | PA | 20-0 | 38-32-13 | D10568 | | | 21 | | | | | | SM00047 | | | | S | 050-099 |
| 685 | 20 | | PA | 15-6 | 38-32-13 | D10568 | | | 21 | | | | | | SM00047 | | | | S | 150-156, 162-165 |
| 685 | 20 | | PA | 15-6 | 38-32-16 | D10568 | | | 21 | | | | | | SM00047 | | | | S | 157, 166-199 |
| 686 | 20 | | PA | 11-0 | 38-32-13 | D10568 | | | 19 | | | | | | GD04444 | | S.. | 2 | | 050-099 |
| 686 | 20 | | PA | 4-8 | 38-32-13 | D10568 | | | 19 | | | | | | GD04874 | | S.. | 2 | | 150-156, 162-165 |
| 686 | 20 | | PA | 4-8 | 38-32-16 | D10568 | | | 19 | | | | | | GD04874 | | S.. | 2 | | 157, 166-199 |
| 688 | 22 | | PA | 24-0 | 38-32-13 | D05116P | | | 5 | | | | | | SM00047 | | | | S | 050-099 |
| 688 | 22 | | PA | 31-0 | 38-32-13 | D05116P | | | 5 | | | | | | SP03814 | | | | S | 150-156, 162-165 |
| 688 | 22 | | PA | 31-0 | 38-32-16 | D05116P | | | 5 | | | | | | SP03814 | | | | S | 157, 166-199 |
| 689 | 18 | | PA | 24-0 | 38-32-13 | D05116P | | | 6 | DK | | | | | SM00046 | | | | S | 050-099 |
| 689 | 22 | | PA | 31-0 | 38-32-13 | D05116P | | | 6 | | | | | | SP03816 | | | | S | 150-156, 162-165 |
| 689 | 22 | | PA | 31-0 | 38-32-16 | D05116P | | | 6 | | | | | | SP03816 | | | | S | 157, 166-199 |
| 690 | 22 | | PA | 57-8 | 33-25-11 | D05114P | | | 20 | | | | | | SM00041 | | | | S | 275-278 |
| 690 | 22 | | PA | 3-11 | 33-25-11 | D05114P | | | 20 | | | | | | SM00041 | | | | S | 280-299 |
| 691 | 20 | | PA | 38-9 | 38-32-13 | SM00036 | | | | | S | | | | D05116P | | | 5 | | 275-276 |
| 691 | 20 | | PA | 38-9 | 38-32-16 | SM00036 | | | | | S | | | | D05116P | | | 5 | | 277-278 |
| 691 | 20 | | PA | 28-7 | 38-32-16 | SM00036 | | | | | S | | | | D05116P | | | 5 | | 280-299 |
| 692 | 18 | | PA | 38-9 | 38-32-13 | SM00037 | | | | | S | | | | D05116P | | | 6 | | 275-276 |
| 692 | 18 | | PA | 38-9 | 38-32-16 | SM00037 | | | | | S | | | | D05116P | | | 6 | | 277-278 |
| 692 | 18 | | PA | 28-7 | 38-32-16 | SM00037 | | | | | S | | | | D05116P | | | 6 | | 280-299 |
| 695 | 20 | | PA | 10-5 | 25-42-11 | SM00045 | | | | | 9 | | | | D00812 | | | 29 | | 275-278 |
| 695 | 20 | | PA | 58-4 | 25-42-11 | SM00045 | | | | | 9 | | | | D00812 | | | 29 | | 280-299 |
| 696 | 16 | | PA | 53-9 | 38-13-11 | D05114P | | | | | 41 | | | | SP00489 | | | | 9 | 150-199 |
| 699 | 20 | | PA | 45-0 | 25-42-11 | D05114P | | | | | 43 | | | | SM00045 | | | | 9 | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 67

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|-----|--|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | | | |
| 699 | 20 | | PA | | 61-11 | 25-42-11 | D05114P | | 43 | | | | | SM00045 | | 9 | | | 150-199 |
| 699 | 20 | | PA | | 61-11 | 25-42-11 | D05114P | | 14 | | | | | SM00045 | | 9 | | | 275-278 |
| 699 | 20 | | PA | | 3-11 | 25-42-11 | D05114P | | 14 | | | | | SM00045 | | 9 | | | 280-299 |
| 701 | 16 | | PA | | 26-6 | 38-13-11 | D10568 | | 8 | | | | | SP00489 | | 9 | | | 150-199 |
| 702 | 16 | | PA | | 4-8 | 38-13-11 | D10568 | | 2 | | | | | GD04874 | A.. | 2 | | | 150-199 |
| 703 | 20 | | PA | | 8-0 | 25-42-11 | D13484 | | 10 | | | | | SM00045 | | 9 | | | 050-099 |
| 703 | 20 | | PA | | 24-7 | 25-42-11 | SM00045 | | | 9 | | | | D13484 | | 10 | | | 150-199 |
| 703 | 20 | | PA | | 11-8 | 25-42-11 | SM00045 | | | 9 | | | | D10568 | | 29 | | | 275-278 |
| 703 | 20 | | PA | | 63-0 | 25-42-11 | SM00045 | | | 9 | | | | D10568 | | 29 | | | 280-299 |
| 704 | 20 | | PA | | 15-0 | 25-42-11 | D13482 | | | 10 | | | | SM00045 | | 9 | | | 050-099 |
| 704 | 20 | | PA | | 34-10 | 25-42-11 | SM00045 | | | 9 | | | | D13482 | | 10 | | | 150-199 |
| 704 | 20 | | PA | | 69-11 | 25-42-11 | SM00045 | | | 9 | | | | D10908 | | 29 | | | 275-278 |
| 704 | 20 | | PA | | 12-7 | 25-42-11 | SM00045 | | | 9 | | | | D10908 | | 29 | | | 280-299 |
| 707 | 22 | | PA | | 23-4 | 33-21-35 | D02944 | | | 2 | | | | D03092 | | 1 | | | 150-199 |
| 708 | 22 | | PA | | 23-4 | 33-21-35 | D02944 | | | 3 | | | | D03092 | | 2 | | | 150-199 |
| 709 | 16 | | PA | | 75-6 | 33-21-35 | D02944 | | | 5 | FM | | | D05114P | | 28 | | | 150-154, 157-165, 167-199 |
| 709 | 16 | | PQ | G9 | 75-6 | 33-21-35 | D02944 | | | 5 | FM | | | D05114P | | 28 | | | 155-156, 166 |
| 709Z | | | | G9 | 0-0 | 33-21-35 | D02944 | | | DED | | | | D05114P | | DED | | | 155-156, 166 |
| 710 | 16 | | PA | | 10-2 | 33-21-35 | D02944 | | | 7 | FM | | | GD04888 | A.. | E | | | 150-154, 157-165, 167-199 |
| 710 | 16 | | PQ | HO | 10-2 | 33-21-35 | D02944 | | | 7 | FM | | | GD04888 | A.. | E | | | 155-156, 166 |
| 710Z | | | | HO | 0-0 | 33-21-35 | D02944 | | | DED | | | | GD04888 | | DED | | | 155-156, 166 |
| 711 | 16 | | PA | | 4-11 | 33-21-35 | D02944 | | | 8 | FM | | | GD02062 | S.. | E | | | 150-199 |
| 712 | 22 | | PA | | 6-6 | 33-21-35 | D02944 | | | 9 | | | | D03124 | | 1 | | | 150-199 |
| 713 | 22 | | PA | | 6-6 | 33-21-35 | D02944 | | | 10 | | | | D03124 | | 2 | | | 150-199 |
| 714 | 22 | | PA | | 3-3 | 33-21-35 | D02944 | | | 11 | | | | SM00052 | | 9 | | | 150-199 |
| 715 | 22 | | PA | | 3-3 | 33-21-35 | D02944 | | | 12 | | | | SM00053 | | 9 | | | 150-199 |
| 716 | 22 | | PA | | 20-7 | 33-21-35 | D03092 | | | 3 | | | | SM00052 | | 9 | | | 150-199 |
| 717 | 22 | | PA | | 20-7 | 33-21-35 | D03092 | | | 4 | | | | SM00053 | | 9 | | | 150-199 |
| 718 | 20 | | PA | | 3-1 | 33-21-35 | D03092 | | | 5 | | | | GD02088 | S.. | E | | | 150-199 |
| 719 | 22 | | PA | | 6-2 | 33-21-35 | D03124 | | | 3 | | | | SM00052 | | 9 | | | 150-199 |
| 720 | 22 | | PA | | 6-2 | 33-21-35 | D03124 | | | 4 | | | | SM00053 | | 9 | | | 150-199 |
| 721 | 20 | | PA | | 3-2 | 33-21-35 | D03124 | | | 5 | | | | GD02062 | S.. | E | | | 150-199 |
| 760 | 20 | | PA | | 54-0 | 33-24-11 | D10568 | | | 30 | | | | D05114P | | 37 | | | 050-099 |
| 760 | 20 | | PA | | 66-5 | 33-24-11 | D10568 | | | 30 | | | | D05114P | | 37 | | | 275-299 |
| 761 | 20 | | PA | | 54-0 | 33-24-11 | D10568 | | | 32 | | | | D05114P | | 38 | | | 050-099 |
| 761 | 20 | | PA | | 66-5 | 33-24-11 | D10568 | | | 32 | | | | D05114P | | 38 | | | 275-299 |
| 762 | 20 | | PA | | 10-11 | 33-24-11 | D10908 | | | 30 | | | | D05114P | | 39 | | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 68

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 762 | 20 | | PA | 11-1 | 33-24-11 | D10908 | | 30 | | | | | D05114P | 39 | | | 280-299 |
| 763 | 20 | | PA | 10-11 | 33-24-11 | D10908 | | 32 | | | | | D05114P | 40 | | | 275-278 |
| 763 | 20 | | PA | 11-1 | 33-24-11 | D10908 | | 32 | | | | | D05114P | 40 | | | 280-299 |
| 773 | 20 | | PA | 16-9 | 33-22-31 | D10908 | | 24 | | | | | GD04194 | A.. | 2 | | 280-299 |
| 774 | 20 | | PA | 16-9 | 33-22-31 | D10908 | | 31 | | | | | GD04194 | A.. | 2 | | 280-299 |
| 775 | 20 | | PA | 11-1 | 33-22-31 | D10908 | | 23 | | | | | D05114P | 32 | | | 280-299 |
| 778 | 20 | | PA | 11-1 | 35-21-12 | D10908 | | 3 | | | | | D05114P | 30 | | | 280-299 |
| 779 | 20 | | PA | 12-3 | 35-21-12 | D10908 | | 4 | | | | | GD01662 | D.. | 2 | | 280-299 |
| 781 | 24 | | PK | 72-0 | 33-21-31 | D05116P | | 14 | | | | | D05114P | 40 | | | 050-099 |
| 781 | 24 | | PK | 80-6 | 33-21-31 | D05116P | | 34 | | | | | D05114P | 7 | | | 162-199 |
| 782 | 20 | | PA | 61-0 | 33-24-11 | D10570 | | 12 | | | | | SM00025 | | S | | 050-099 |
| 783 | 20 | | PA | 53-0 | 33-26-21 | D05114P | | 30 | | | | | SM00072 | | 9 | | 050-099 |
| 784 | 20 | | PA | 2-0 | 33-26-21 | D10568 | | 14 | | | | | SM00072 | | 9 | | 050-099 |
| 785 | 22 | | PA | 29-0 | 33-25-11 | SM00075 | | | | S | | | SM00073 | | S | | 050-099 |
| 786 | 22 | | PA | 29-0 | 33-25-11 | SM00076 | | | | S | | | SM00074 | | S | | 050-099 |
| 800 | 20 | | PA | 40-6 | 33-24-11 | SP03578 | | 9 | | | | | D13414 | 12 | | | 150-199 |
| 801 | 20 | | PA | 15-1 | 33-24-11 | SP01586 | | 9 | | | | | D00812 | 12 | | | 150-199 |
| 802 | 20 | | PA | 8-0 | 26-13-11 | D13484 | | 4 | | | | | SM00056 | | 9 | | 050-099 |
| 802 | 20 | | PA | 9-4 | 26-13-11 | SM00056 | | 9 | | | | | D13484 | 4 | | | 150-199 |
| 803 | 20 | | PA | 8-0 | 26-13-11 | D13484 | | 3 | | | | | SM00055 | | 9 | | 050-099 |
| 803 | 20 | | PA | 9-4 | 26-13-11 | SM00055 | | 9 | | | | | D13484 | 3 | | | 150-199 |
| 804 | 20 | | PA | 8-0 | 26-13-11 | D13484 | | 2 | | | | | SM00054 | | 9 | | 050-099 |
| 804 | 20 | | PA | 9-4 | 26-13-11 | SM00054 | | 9 | | | | | D13484 | 2 | | | 150-199 |
| 805 | 22 | | PA | 31-0 | 33-26-11 | D05116P | | 2 | | | | | SP03668 | | 9 | | 150-199 |
| 807 | 20 | | PA | 62-0 | 33-21-33 | D05114P | | 42 | | | | | D02008 | 5 | | | 150-154, 157-165, 167-199 |
| 807 | 20 | | PQ | Q7 | 62-0 | 33-21-33 | D05114P | 42 | | | | | D02008 | 5 | | | 155-156, 166 |
| 807Z | | | | Q7 | 0-0 | 33-21-33 | D05114P | DED | | | | | D02008 | DED | | | 155-156, 166 |
| 809 | 20 | | PA | | 40-6 | 33-26-21 | SP03676 | | | 9 | | | D13414 | 13 | | | 150-199 |
| 810 | 20 | | PA | | 51-0 | 33-26-21 | D05114P | 6 | | | | | D13484 | 11 | | | 050-099 |
| 810 | 20 | | PA | | 52-0 | 33-26-21 | D13484 | 11 | | | | | SP03672 | | 9 | | 150-199 |
| 811 | 20 | | PA | | 51-0 | 33-26-21 | D05114P | 7 | | | | | D13484 | 12 | | | 050-099 |
| 811 | 20 | | PA | | 52-0 | 33-26-21 | D13484 | 12 | | | | | SP03674 | | 9 | | 150-199 |
| 812 | 20 | | PA | | 54-0 | 33-26-21 | D05114P | 8 | | | | | D00812 | 10 | | | 050-099 |
| 812 | 20 | | PA | | 15-1 | 33-26-21 | D00812 | 10 | | | | | SP03622 | | 9 | | 150-199 |
| 818 | 22 | | PA | | 10-0 | 33-25-11 | D00812 | 7 | | | | | SM00075 | | S | | 050-099 |
| 818 | 22 | | PA | | 15-1 | 33-25-11 | D00812 | 7 | | | | | SP03702 | | 9 | | 150-199 |
| 819 | 20 | | PA | | 10-0 | 33-25-11 | D00812 | 26 | | | | | GD03844 | D.. | E | | 050-099 |
| 819 | 22 | | PA | | 9-4 | 33-25-11 | D00812 | 26 | | | | | GD04976 | A.. | E | | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 69

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|-----------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 819 | 20 | PA | | | 2-6 | 33-25-11 | D00812 | | 26 | | | | GD04978 | D.. | E | | 155-199 |
| 820 | 20 | PA | | | 11-0 | 33-25-11 | D10568 | | 26 | | | | GD04444 | D.. | 2 | | 050-099 |
| 820 | 20 | PA | | | 4-8 | 33-25-11 | D10568 | | 26 | | | | GD04874 | D.. | 2 | | 150-199 |
| 821 | 22 | PA | | | 16-0 | 33-25-11 | D10568 | | 9 | | | | SM00076 | | S | | 050-099 |
| 821 | 22 | PA | | | 26-6 | 33-25-11 | D10568 | | 9 | | | | SP03628 | | 9 | | 150-199 |
| 822 | 22 | PA | | | 42-0 | 33-25-11 | D10568 | | 25 | | | | D05116P | | 16 | | 050-099 |
| 822 | 22 | PA | | | 26-6 | 33-25-11 | D10568 | | 25 | | | | SP00574 | | S | | 150-154, 156, 162-199 |
| 822 | 22 | PA | | | 53-9 | 33-25-11 | D10568 | | 25 | | | | D05116P | | 20 | | 155, 157 |
| 823 | 22 | PA | | | 16-0 | 33-25-11 | D10568 | | 7 | | | | SM00075 | | S | | 050-099 |
| 823 | 22 | PA | | | 26-6 | 33-25-11 | D10568 | | 7 | | | | SP03702 | | 9 | | 150-199 |
| 824 | 22 | PA | | | 22-0 | 33-25-11 | SP00570 | | | S | | | D05116P | | 13 | | 050-099 |
| 824 | 22 | PA | | | 61-2 | 33-25-11 | D05116P | | 13 | | | | SP00576 | | S | | 150-199 |
| 825 | 22 | PA | | | 10-0 | 33-25-11 | D00812 | | 9 | | | | SM00076 | | S | | 050-099 |
| 825 | 22 | PA | | | 41-9 | 33-25-11 | D05116P | | 14 | | | | D00812 | | 9 | | 150-199 |
| 836 | 20 | PA | | | 16-0 | 26-13-11 | D13490 | | 1 | | | | D05116P | | 27 | | 050-099 |
| 836 | 20 | PA | | | 13-0 | 26-13-11 | D13486 | | 1 | | | | D05116P | | 27 | | 150-199 |
| 837 | 20 | PA | | | 16-0 | 26-13-11 | D13490 | | 2 | | | | D05116P | | 30 | | 050-099 |
| 837 | 20 | PA | | | 41-4 | 26-13-11 | D13486 | | 2 | | | | SP03614 | | 9 | | 150-199 |
| 838 | 20 | PA | | | 16-0 | 26-13-11 | D13490 | | 3 | | | | D05116P | | 31 | | 050-099 |
| 838 | 20 | PA | | | 41-4 | 26-13-11 | D13486 | | 3 | | | | SP03616 | | 9 | | 150-199 |
| 839 | 20 | PA | | | 16-0 | 26-13-11 | D13490 | | 4 | | | | D05116P | | 32 | | 050-099 |
| 839 | 20 | PA | | | 41-4 | 26-13-11 | D13486 | | 4 | | | | SP03618 | | 9 | | 150-199 |
| 840 | 18 | PA | | | 72-0 | 26-13-11 | D05114P | | 34 | | | | D05116P | | 25 | DK | 050-099 |
| 840 | 20 | PA | | | 80-6 | 26-13-11 | D05114P | | 19 | | | | D05116P | | 25 | | 150-157 |
| 840 | 18 | PA | | | 80-6 | 26-13-11 | D05114P | | 19 | DL | | | D05116P | | 25 | DK | 162-199 |
| 841 | 20 | PA | | | 72-0 | 26-13-11 | D05114P | | 20 | | | | D05116P | | 26 | | 050-099 |
| 841 | 20 | PA | | | 80-6 | 26-13-11 | D05114P | | 20 | | | | D05116P | | 26 | | 150-199 |
| 842 | 20 | PA | | | 31-0 | 26-13-11 | SP03610 | | | 9 | | | D05116P | | 28 | | 150-199 |
| 843 | 20 | PA | | | 31-0 | 26-13-11 | SP03612 | | | 9 | | | D05116P | | 29 | | 150-199 |
| 844 | 20 | PA | | | 31-0 | 26-13-11 | SP03614 | | | 9 | | | D05116P | | 30 | | 150-199 |
| 845 | 20 | PA | | | 31-0 | 26-13-11 | SP03616 | | | 9 | | | D05116P | | 31 | | 150-199 |
| 846 | 20 | PA | | | 31-0 | 26-13-11 | SP03618 | | | 9 | | | D05116P | | 32 | | 150-199 |
| 847 | 20 | PA | | | 51-0 | 26-13-11 | D05114P | | 25 | | | | D13484 | | 1 | | 050-099 |
| 847 | 20 | PA | | | 44-8 | 26-13-11 | SP03600 | | | S | | | D13484 | | 1 | | 150-157 |
| 847 | 20 | PA | | | 44-8 | 26-13-11 | SP03600 | | | 9 | | | D13484 | | 1 | | 162-199 |
| 848 | 20 | PA | | | 53-0 | 26-13-11 | D13482 | | 1 | | | | D05114P | | 26 | | 050-099 |
| 848 | 20 | PA | | | 47-2 | 26-13-11 | SP03598 | | | S | | | D13482 | | 1 | | 150-157 |
| 848 | 20 | PA | | | 47-2 | 26-13-11 | SP03598 | | | 9 | | | D13482 | | 1 | | 162-199 |
| 849 | 20 | PA | | | 45-0 | 26-13-11 | D05114P | | 27 | | | | SM00054 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 70

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|--|--|-----|----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | | | | |
| 849 | 20 | PA | | 36-4 | 26-13-11 | SP03604 | | | | | | | | 9 | SM00054 | | | | 9 | 150-199 |
| 850 | 20 | PA | | 45-0 | 26-13-11 | D05114P | | | | | 28 | | | | SM00055 | | | | 9 | 050-099 |
| 850 | 20 | PA | | 36-4 | 26-13-11 | SP03606 | | | | | | | | 9 | SM00055 | | | | 9 | 150-199 |
| 851 | 20 | PA | | 45-0 | 26-13-11 | D05114P | | | | | 29 | | | | SM00056 | | | | 9 | 050-099 |
| 851 | 20 | PA | | 36-4 | 26-13-11 | SP03608 | | | | | | | | 9 | SM00056 | | | | 9 | 150-199 |
| 852 | 20 | PA | | 15-0 | 26-13-11 | D13482 | | | | | 2 | | | | SM00054 | | | | 9 | 050-099 |
| 852 | 20 | PA | | 11-10 | 26-13-11 | SM00054 | | | | | | | | 9 | D13482 | | | 2 | | 150-199 |
| 853 | 20 | PA | | 15-0 | 26-13-11 | D13482 | | | | | 3 | | | | SM00055 | | | | 9 | 050-099 |
| 853 | 20 | PA | | 11-10 | 26-13-11 | SM00055 | | | | | | | | 9 | D13482 | | | 3 | | 150-199 |
| 854 | 20 | PA | | 15-0 | 26-13-11 | D13482 | | | | | 4 | | | | SM00056 | | | | 9 | 050-099 |
| 854 | 20 | PA | | 11-10 | 26-13-11 | SM00056 | | | | | | | | 9 | D13482 | | | 4 | | 150-199 |
| 855 | 22 | PA | | 19-0 | 33-25-11 | SM00074 | | | | | | | | S | D05116P | | | 17 | | 050-099 |
| 855 | 22 | PA | | 21-1 | 33-25-11 | D05116P | | | | | 17 | | | | SP03694 | | | | 9 | 150-199 |
| 860 | 22 | PA | | 26-6 | 33-26-11 | D10568 | | | | | 15 | | | | SP03908 | | | | 9 | 150-199 |
| 862 | 22 | PA | | 4-8 | 33-26-11 | D10568 | | | | | 1 | | | | GD04874 | | | A.. | 2 | 150-199 |
| 863 | 22 | PA | | 31-0 | 33-26-11 | SP03906 | | | | | | | | 9 | D05116P | | | | 9 | 150-199 |
| 870 | 22 | PA | | 15-1 | 33-26-11 | D00812 | | | | | 15 | | | | SP03908 | | | | 9 | 150-199 |
| 871 | 22 | PA | | 31-0 | 33-26-11 | D05116P | | | | | 3 | | | | SP03908 | | | | 9 | 150-199 |
| 874 | 20 | PA | | 8-0 | 33-26-21 | L00403 | | | | | G | C | | | GD00723 | | | A.. | 2 | 050-099 |
| 879 | 20 | PA | | 13-0 | 33-26-21 | L00403 | | | | | G | C | | | GD01120 | | | A.. | 2 | 150-199 |
| 880 | 20 | PA | | 63-0 | 33-26-21 | L00403 | | | | | P | C | | | D05116P | | | | 21 | 050-099 |
| 880 | 20 | PA | | 69-2 | 33-26-21 | L00403 | | | | | P | C | | | D05116P | | | | 21 | 150-199 |
| 881 | 20 | PA | | 55-0 | 33-26-21 | L00403 | | | | | S | C | | | SM00077 | | | | S | 050-099 |
| 881 | 20 | PA | | 79-6 | 33-26-21 | L00403 | | | | | S | C | | * | D13486 | | | | 12 | 150-199 |
| 882 | 20 | PA | | 15-0 | 33-26-21 | D05116P | | | | | 9 | | | | SM00077 | | | | S | 050-099 |
| 882 | 20 | PA | | 81-3 | 33-26-21 | L00403 | | | | | S | C | | * | SP03626 | | | | 9 | 150-199 |
| 883 | 20 | PA | | 16-0 | 33-26-21 | D13490 | | | | | 11 | | | | D05116P | | | | 28 | 050-099 |
| 883 | 20 | PA | | 13-0 | 33-26-21 | D13486 | | | | | 11 | | | | D05116P | | | | 22 | 150-199 |
| 884 | 20 | PA | | 20-0 | 33-26-21 | D10570 | | | | | 10 | | | | D05116P | | | | 29 | 050-099 |
| 884 | 20 | PA | | 40-6 | 33-26-21 | SP03624 | | | | | | 9 | | | D13414 | | | | 10 | 150-199 |
| 887 | 18 | PA | | 26-6 | 33-26-11 | SP03906 | | | | | | 9 | | | D10568 | | | | 6 | 150-199 |
| 888 | 20 | PA | | 26-6 | 33-26-11 | SP03668 | | | | | | 9 | | | D10568 | | | | 17 | 150-199 |
| 890 | 22 | PA | | 12-0 | 33-26-11 | SM00001 | | | | | | | | 9 | SP03906 | | | | 9 | 150-199 |
| 891 | 22 | PA | | 50-4 | 38-32-12 | D13414 | | | | | | 18 | | | GD03918 | | | D.. | E | 150-154 |
| 891 | 20 | PA | | 50-4 | 38-32-12 | D13414 | | | | | | 18 | | | GD03918 | | | D.. | E | 155-156, 162-165 |
| 891 | 20 | PA | | 50-4 | 38-32-16 | D13414 | | | | | | 18 | | | GD03918 | | | D.. | E | 157, 166-199 |
| 892 | 22 | PA | | 50-4 | 38-32-12 | D13414 | | | | | | 19 | | | GD03860 | | | S.. | E | 150-154 |
| 892 | 20 | PA | | 50-4 | 38-32-12 | D13414 | | | | | | 19 | | | GD03860 | | | S.. | E | 155-156, 162-165 |
| 892 | 20 | PA | | 50-4 | 38-32-16 | D13414 | | | | | | 19 | | | GD03860 | | | S.. | E | 157, 166-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 71

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0814 | 286T0814 | | | MID GALLEY & SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 893 | 18 | | PA | 40-6 | 38-32-12 | D13414 | | 20 | DK | | | | SP03818 | | S | | 150-156, 162-165 |
| 893 | 18 | | PA | 40-6 | 38-32-16 | D13414 | | 20 | DK | | | | SP03818 | | S | | 157, 166-199 |
| 894 | 22 | | PA | 40-6 | 38-32-12 | D13414 | | 21 | | | | | SP03819 | | S | | 150-155, 162-165 |
| 894 | 22 | | PA | 40-6 | 38-32-16 | D13414 | | 21 | | | | | SP03819 | | S | | 156-157, 166-199 |
| 895 | 22 | | PA | 90-0 | 33-26-11 | D13414 | | 15 | | | | | D05114P | 3 | | | 150-199 |
| 896 | 20 | | PA | 12-3 | 33-26-11 | D13414 | | 17 | | | | | D05116P | 33 | | | 150-199 |
| 897 | 18 | | PA | 40-6 | 33-26-11 | D13414 | | 6 | | | | | SP03910 | | 9 | | 150-199 |
| 898 | 20 | | PA | 3-6 | 33-26-11 | D13414 | | 1 | | | | | GD04866 | A.. | E | | 150-199 |
| 899 | 20 | | PA | 20-0 | 33-26-21 | D10570 | | 13 | | | | | D05116P | 22 | | | 050-099 |
| 900 | 16 | | PA | 40-6 | 38-13-11 | D13414 | | 8 | | | | | SP00491 | | 9 | | 150-199 |
| 901 | 16 | | PA | 3-6 | 38-13-11 | D13414 | | 2 | | | | | GD04866 | A.. | E | | 150-199 |
| W0815 | 286T0815 | | | SATCOM E9 TO E11,M1791 | | | | | | | | | | | | | |
| 001 | 24 | | PK | 38-0 | 23-25-11 | D06161J | | 3 | | | | | D02685 | | H | | 156-157, 166-199, 277-299 |
| 002 | 24 | | PK | 38-0 | 23-25-11 | D06161J | | 4 | | | | | D02685 | | B | | 156-157, 166-199, 277-299 |
| 005 | 20 | | PA | 45-0 | 23-25-11 | D06161J | | 2 | | | | | D06163P | 3 | | | 156-157, 166-199, 277-299 |
| 006 | 20 | | PA | 2-0 | 23-25-11 | D06163P | | 2 | | | | | GD01758 | A.. | 2 | | 156-157, 166-199, 277-299 |
| 007 | 20 | | PA | 2-0 | 23-25-11 | D06163P | | 1 | | | | | GD01758 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 009 | 20 | | PA | 38-0 | 23-25-11 | D02685 | | F | | | | | D06161J | 1 | | | 156-157, 166-199, 277-299 |
| 010 | 20 | | PA | 2-0 | 23-25-11 | D02685 | | E | | | | | GD06897 | A.. | E | | 156-157, 166-199, 277-299 |
| 011 | 20 | | PA | 2-0 | 23-25-11 | D02685 | | A | | | | | GD06899 | S.. | E | | 156-157, 166-199, 277-299 |
| 201 | 20 | | UA | 1-6 | 23-25-11 | D06163P | | REF | | IA | | | GD01758 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 201B | 24 | | PW IA | 45-0 | 23-25-11 | D06161J | | 7 | | | | | D06163P | 6 | | | 156-157, 166-199, 277-299 |
| 201R | 24 | | PW IA | 0-0 | 23-25-11 | D06161J | | 6 | | | | | D06163P | 5 | | | 156-157, 166-199, 277-299 |
| 201Z | | | IA | 0-0 | 23-25-11 | D06161J | | 5 | | | | | D06163P | REF | | IA | 156-157, 166-199, 277-299 |
| 202 | 20 | | UA | 1-6 | 23-25-11 | D06163P | | REF | | IB | | | GD01758 | S.. | 2 | | 156-157, 166-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 72
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0815 | 286T0815 | | | SATCOM E9 TO E11,M1791 (continued) | | | | | | | | | | | | |
| 202B | 24 | PW | IB | 45-0 | 23-25-11 | D06161J | | 9 | | | | D06163P | 8 | | | 156-157, 166-199, 277-299 |
| 202R | 24 | PW | IB | 0-0 | 23-25-11 | D06161J | | 8 | | | | D06163P | 7 | | | 156-157, 166-199, 277-299 |
| 202Z | | | IB | 0-0 | 23-25-11 | D06161J | | 10 | | | | D06163P | REF | IB | | 156-157, 166-199, 277-299 |
| FRA | | | | 0-0 | 23-25-11 | D06163P | | 4 | | | | D06163P | REF | IA | | 156-157, 166-199, 277-299 |
| FRB | | | | 0-0 | 23-25-11 | D06163P | | 9 | | | | D06163P | REF | IB | | 156-157, 166-199, 277-299 |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS | | | | | | | | | | | | |
| 001 | 22 | PA | | 8-0 | 33-27-11 | D02882 | | 2 | | | | SP01320 | 9 | | | 050-099 |
| 001 | 22 | PA | | 3-7 | 33-27-11 | D02882 | | 2 | | | | SP01320 | 9 | | | 150-199, 275-299 |
| 002 | 22 | PA | | 8-0 | 33-27-11 | D02882 | | 3 | | | | SP01318 | 9 | | | 050-099 |
| 002 | 22 | PA | | 3-7 | 33-27-11 | D02882 | | 3 | | | | SP01318 | 9 | | | 150-199, 275-299 |
| 003 | 22 | PA | | 62-0 | 33-27-11 | D02882 | | 5 | | | | D05118P | 8 | | | 050-099 |
| 003 | 22 | PA | | 73-8 | 33-27-11 | D02882 | | 5 | | | | D05118P | 8 | | | 150-199, 275-299 |
| 004 | 20 | PA | | 8-0 | 33-27-11 | D02882 | | 7 | | | | GD00070 | A.. | 2 | | ALL |
| 005 | 22 | PA | | 13-0 | 33-27-11 | D02882 | | 8 | | | | L00207 | =G | E | * | 050-099 |
| 005 | 22 | PA | | 9-8 | 33-27-11 | D02882 | | 8 | | | | L00207 | =G | E | * | 150-199, 275-299 |
| 006 | 22 | PA | | 15-0 | 33-27-11 | D02882 | | 9 | | | | SP01298 | 9 | | | 050-099 |
| 006 | 22 | PA | | 8-4 | 33-27-11 | D02882 | | 9 | | | | SP01298 | 9 | | | 150-199, 275-299 |
| 007 | 22 | PA | | 15-0 | 33-27-11 | D02882 | | 10 | | | | SP01300 | 9 | | | 050-099 |
| 007 | 22 | PA | | 8-4 | 33-27-11 | D02882 | | 10 | | | | SP01300 | 9 | | | 150-199, 275-299 |
| 008 | 22 | PA | | 11-0 | 33-27-11 | D02882 | | 11 | | | | SP01304 | 9 | | | 050-099 |
| 008 | 22 | PA | | 8-10 | 33-27-11 | D02882 | | 11 | | | | SP01304 | 9 | | | 150-199, 275-299 |
| 009 | 22 | PA | | 11-0 | 33-27-11 | D02882 | | 12 | | | | SP01302 | 9 | | | 050-099 |
| 009 | 22 | PA | | 8-10 | 33-27-11 | D02882 | | 12 | | | | SP01302 | 9 | | | 150-199, 275-299 |
| 010 | 22 | PA | | 15-0 | 33-27-11 | SP01286 | | 9 | | | | SP01302 | 9 | | | 050-099 |
| 010 | 22 | PA | | 10-4 | 33-27-11 | SP01286 | | 9 | | | | SP01302 | 9 | | | 150-199, 275-299 |
| 011 | 22 | PA | | 15-0 | 33-27-11 | SP01288 | | 9 | | | | SP01304 | 9 | | | 050-099 |
| 011 | 22 | PA | | 10-4 | 33-27-11 | SP01288 | | 9 | | | | SP01304 | 9 | | | 150-199, 275-299 |
| 013 | 20 | PA | | 12-0 | 33-27-11 | L00207 | | =G | E | * | | GD00932 | S.. | 2 | | 050-099 |
| 013 | 20 | PA | | 10-8 | 33-27-11 | L00207 | | =G | E | * | | GD00932 | S.. | 2 | | 150-199, 275-299 |
| 014 | 22 | PA | | 9-0 | 33-27-11 | D02878 | | 2 | | | | SP01292 | 9 | | | 050-099 |
| 014 | 22 | PA | | 6-8 | 33-27-11 | D02878 | | 2 | | | | SP01292 | 9 | | | 150-199, 275-299 |
| 015 | 22 | PA | | 9-0 | 33-27-11 | D02878 | | 3 | | | | SP01290 | 9 | | | 050-099 |
| 015 | 22 | PA | | 6-8 | 33-27-11 | D02878 | | 3 | | | | SP01290 | 9 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 73

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 016 | 20 | | PA | 67-0 | 33-27-11 | D02878 | | 5 | | | | | D05118P | 11 | | | 050-099 |
| 016 | 20 | | PA | 77-2 | 33-27-11 | D02878 | | 5 | | | | | D05118P | 11 | | | 150-199, 275-299 |
| 017 | 20 | | PA | 10-0 | 33-27-11 | D02878 | | 7 | | | | | GD00932 | A.. | 2 | | 050-099 |
| 017 | 20 | | PA | 12-2 | 33-27-11 | D02878 | | 7 | | | | | GD00932 | A.. | 2 | | 150-199, 275-299 |
| 018 | 20 | | PA | 8-0 | 33-27-11 | D02878 | | 8 | | | | | L00203 | =G | E | * | 050-099 |
| 018 | 20 | | PA | 3-3 | 33-27-11 | D02878 | | 8 | | | | | L00203 | =G | E | * | 150-199, 275-299 |
| 019 | 22 | | PA | 6-0 | 33-27-11 | D02878 | | 9 | | | | | SP01306 | | 9 | | 050-099 |
| 019 | 22 | | PA | 3-3 | 33-27-11 | D02878 | | 9 | | | | | SP01306 | | 9 | | 150-199, 275-299 |
| 020 | 22 | | PA | 6-0 | 33-27-11 | D02878 | | 10 | | | | | SP01308 | | 9 | | 050-099 |
| 020 | 22 | | PA | 3-3 | 33-27-11 | D02878 | | 10 | | | | | SP01308 | | 9 | | 150-199, 275-299 |
| 021 | 22 | | PA | 7-0 | 33-27-11 | D02878 | | 11 | | | | | SP01312 | | 9 | | 050-099 |
| 021 | 22 | | PA | 3-3 | 33-27-11 | D02878 | | 11 | | | | | SP01312 | | 9 | | 150-199, 275-299 |
| 022 | 22 | | PA | 7-0 | 33-27-11 | D02878 | | 12 | | | | | SP01310 | | 9 | | 050-099 |
| 022 | 22 | | PA | 3-3 | 33-27-11 | D02878 | | 12 | | | | | SP01310 | | 9 | | 150-199, 275-299 |
| 023 | 22 | | PA | 11-0 | 33-27-11 | SP01310 | | | 9 | | | | SP01272 | | 9 | | 050-099 |
| 023 | 22 | | PA | 6-9 | 33-27-11 | SP01310 | | | 9 | | | | SP01272 | | 9 | | 150-199, 275-299 |
| 024 | 22 | | PA | 11-0 | 33-27-11 | SP01312 | | | 9 | | | | SP01270 | | 9 | | 050-099 |
| 024 | 22 | | PA | 6-9 | 33-27-11 | SP01312 | | | 9 | | | | SP01270 | | 9 | | 150-199, 275-299 |
| 026 | 20 | | PA | 16-0 | 33-27-11 | L00203 | | =G | E | * | | | GD00070 | S.. | 2 | | 050-099 |
| 026 | 20 | | PA | 12-6 | 33-27-11 | L00203 | | =G | E | * | | | GD00932 | S.. | 2 | | 150-199, 275-299 |
| 035 | 20 | | PA | 15-8 | 33-21-14 | D05118P | | 5 | | | | | SM00001 | | 9 | | 150-199, 275-299 |
| 036 | 20 | | PA | 7-10 | 33-21-14 | D11212 | | 5 | | | | | SM00001 | | 9 | | 150-199, 275-299 |
| 037 | 20 | | PA | 15-0 | 33-21-14 | D11216 | | 5 | | | | | SM00001 | | 9 | | 150-199, 275-299 |
| 059 | 20 | | PA | 6-6 | 33-21-14 | L00769 | | =G | E | | | | GD04932 | S.. | E | | 150-199, 275-299 |
| 070 | 20 | | PA | 5-1 | 33-21-14 | L00773 | | =G | E | | | | GD04948 | S.. | E | | 150-199, 275-299 |
| 081 | 20 | | PA | 24-10 | 33-21-14 | SP02978 | | | 9 | | | | SP02970 | | 9 | | 150-199, 275-299 |
| 082 | 20 | | PA | 24-10 | 33-21-14 | SP02980 | | | 9 | | | | SP02972 | | 9 | | 150-199, 275-299 |
| 083 | 20 | | PA | 6-11 | 33-21-14 | L00768 | | =G | E | | | | GD04926 | S.. | E | | 150-199, 275-299 |
| 105 | 22 | | PA | 17-0 | 33-21-34 | D05118P | | | 9 | | | | SM00002 | | 9 | | 050-099 |
| 105 | 20 | | PA | 15-8 | 33-21-34 | D05118P | | | 9 | | | | SM00002 | | 9 | | 150-154, 157-165, 167-199, 275-299 |
| 105 | 20 | | PQ | A | 15-8 | 33-21-34 | D05118P | | 9 | | | | SM00002 | | 9 | | 155-156, 166 |
| 105Z | | | | A | 0-0 | 33-21-34 | D05118P | | DED | | | | SM00002 | DED | | | 155-156, 166 |
| 106 | 22 | | PA | 36-0 | 33-21-34 | D05118P | | | 10 | | | | D02006 | | 5 | | 050-099 |
| 106 | 20 | | PA | 35-11 | 33-21-34 | D05118P | | | 10 | | | | D02006 | 5 | FM | | 150-154, 157 |
| 106 | 20 | | PQ | EF | 35-11 | 33-21-34 | D05118P | | 10 | | | | D02006 | 5 | FM | | 155-156 |
| 106 | 22 | | PA | 48-0 | 33-21-34 | D05118P | | | 10 | | | | D02006 | 5 | | | 162-165, 167-199 |
| 106 | 22 | | PQ | EF | 48-0 | 33-21-34 | D05118P | | 10 | | | | D02006 | 5 | | | 166 |
| 106 | 16 | | PA | 50-7 | 33-21-34 | D05118P | | | 10 | | | | D02006 | 5 | FM | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 74
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|--------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 106Z | | | | EF | 0-0 | 33-21-34 | D05118P | | DED | | | | D02006 | DED | | | 155-156, 166 |
| 107 | 18 | PA | | | 4-0 | 33-21-34 | GD01038 | | A.. | E | | | D01988 | 7 | DK | | 050-099 |
| 107 | 20 | PA | | | 21-7 | 33-21-34 | GD04208 | | A.. | E | | | D01988 | 7 | | | 150-154, 157 |
| 107 | 20 | PQ | C | | 21-7 | 33-21-34 | GD04208 | | A.. | E | | | D01988 | 7 | | | 155-156 |
| 107 | 16 | PA | | | 21-7 | 33-21-34 | GD04208 | | A.. | E | | | D01988 | 7 | FM | | 162-165, 167-199 |
| 107 | 16 | PQ | C | | 21-7 | 33-21-34 | GD04208 | | A.. | E | | | D01988 | 7 | FM | | 166 |
| 107 | 20 | PA | | | 7-2 | 33-21-34 | GD04910 | | A.. | E | | | D01988 | 7 | | | 275-299 |
| 107Z | | | | C | 0-0 | 33-21-34 | GD04208 | | DED | | | | D01988 | DED | | | 155-156, 166 |
| 108 | 18 | PA | | | 4-0 | 33-21-34 | GD01564 | | S.. | E | | | D01988 | 8 | DK | | 050-099 |
| 108 | 20 | PA | | | 21-7 | 33-21-34 | GD04634 | | S.. | E | | | D01988 | 8 | | | 150-157 |
| 108 | 16 | PA | | | 21-7 | 33-21-34 | GD04634 | | S.. | E | | | D01988 | 8 | FM | | 162-199 |
| 108 | 20 | PA | | | 7-1 | 33-21-34 | GD04914 | | S.. | E | | | D01988 | 8 | | | 275-299 |
| 109 | 18 | PA | | | 11-0 | 33-21-34 | D05118P | | 3 | | | | D01988 | 5 | DK | | 050-099 |
| 109 | 20 | PA | | | 18-9 | 33-21-34 | D05118P | | 3 | | | | D01988 | 5 | | | 150-154, 157 |
| 109 | 20 | PQ | B | | 18-9 | 33-21-34 | D05118P | | 3 | | | | D01988 | 5 | | | 155-156 |
| 109 | 16 | PA | | | 11-3 | 33-21-34 | D05118P | | 3 | | | | D01988 | 5 | FM | | 162-165, 167-199 |
| 109 | 16 | PQ | B | | 11-3 | 33-21-34 | D05118P | | 3 | | | | D01988 | 5 | FM | | 166 |
| 109 | 20 | PA | | | 14-6 | 33-21-34 | SM00002 | | | 9 | | | D01988 | 5 | | | 275-299 |
| 109Z | | | | B | 0-0 | 33-21-34 | D05118P | | DED | | | | D01988 | DED | | | 155-156, 166 |
| 110 | 22 | PA | | | 5-0 | 33-21-34 | SM00002 | | | 9 | | | D02004 | 5 | | | 050-099 |
| 110 | 20 | PA | | | 6-10 | 33-21-34 | SM00002 | | | 9 | | | D02004 | 5 | | | 150-154, 157-165, 167-199, 275-299 |
| 110 | 20 | PQ | EJ | | 6-10 | 33-21-34 | SM00002 | | | 9 | | | D02004 | 5 | | | 155-156, 166 |
| 110Z | | | | EJ | 0-0 | 33-21-34 | SM00002 | | DED | | | | D02004 | DED | | | 155-156, 166 |
| 111 | 20 | PA | | | 5-0 | 33-21-34 | GD01566 | | A.. | E | | | D02004 | 7 | | | 050-099 |
| 111 | 20 | PA | | | 3-2 | 33-21-34 | GD04882 | | A.. | E | | | D02004 | 7 | | | 150-154, 157-165, 167-199, 275-299 |
| 111 | 20 | PQ | E | | 3-2 | 33-21-34 | GD04882 | | A.. | E | | | D02004 | 7 | | | 155-156, 166 |
| 111Z | | | | E | 0-0 | 33-21-34 | GD04882 | | DED | | | | D02004 | DED | | | 155-156, 166 |
| 112 | 20 | PA | | | 5-0 | 33-21-34 | GD01568 | | S.. | E | | | D02004 | 8 | | | 050-099 |
| 112 | 20 | PA | | | 3-3 | 33-21-34 | GD04886 | | S.. | E | | | D02004 | 8 | | | 150-199, 275-299 |
| 113 | 22 | PA | | | 13-0 | 33-21-34 | D01988 | | 2 | | | | D03150 | 1 | | | 050-099 |
| 113 | 22 | PA | | | 15-3 | 33-21-34 | D01988 | | 2 | | | | D03150 | 1 | | | 150-199 |
| 113 | 22 | PA | | | 11-0 | 33-21-34 | D01988 | | 2 | | | | D03150 | 1 | | | 275-299 |
| 114 | 22 | PA | | | 13-0 | 33-21-34 | D01988 | | 3 | | | | D03150 | 2 | | | 050-099 |
| 114 | 22 | PA | | | 15-3 | 33-21-34 | D01988 | | 3 | | | | D03150 | 2 | | | 150-199 |
| 114 | 22 | PA | | | 11-0 | 33-21-34 | D01988 | | 3 | | | | D03150 | 2 | | | 275-299 |
| 115 | 22 | PA | | | 8-0 | 33-21-34 | SM00003 | | | 9 | | | D03150 | 3 | | | 050-099 |
| 115 | 22 | PA | | | 7-8 | 33-21-34 | SM00003 | | | 9 | | | D03150 | 3 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 75

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | |
| 116 | 22 | | PA | | 8-0 | 33-21-34 | SM00004 | | | | D03150 | | | | 050-099 |
| 116 | 22 | | PA | | 7-8 | 33-21-34 | SM00004 | | | | D03150 | | | | 150-199, 275-299 |
| 117 | 22 | | PA | | 27-0 | 33-21-34 | SM00003 | | | | D03130 | | | | 050-099 |
| 117 | 22 | | PA | | 9-5 | 33-21-34 | SM00005 | | | | D03152 | | | | 150-199, 275-299 |
| 118 | 22 | | PA | | 27-0 | 33-21-34 | SM00004 | | | | D03130 | | | | 050-099 |
| 118 | 22 | | PA | | 9-5 | 33-21-34 | SM00006 | | | | D03152 | | | | 150-199, 275-299 |
| 119 | 22 | | PA | | 28-0 | 33-21-34 | D01988 | | 9 | | D03130 | | | | 050-099 |
| 119 | 22 | | PA | | 13-1 | 33-21-34 | D02004 | | 9 | | D03152 | | | | 150-199, 275-299 |
| 120 | 22 | | PA | | 28-0 | 33-21-34 | D01988 | | 10 | | D03130 | | | | 050-099 |
| 120 | 22 | | PA | | 13-1 | 33-21-34 | D02004 | | 10 | | D03152 | | | | 150-199, 275-299 |
| 121 | 22 | | PA | | 7-0 | 33-21-34 | D01988 | | 11 | | SM00003 | | 9 | | 050-099 |
| 121 | 22 | | PA | | 8-8 | 33-21-34 | D01988 | | 11 | | SM00003 | | 9 | | 150-199 |
| 121 | 22 | | PA | | 3-11 | 33-21-34 | D01988 | | 11 | | SM00003 | | 9 | | 275-299 |
| 122 | 22 | | PA | | 7-0 | 33-21-34 | D01988 | | 12 | | SM00004 | | 9 | | 050-099 |
| 122 | 22 | | PA | | 8-8 | 33-21-34 | D01988 | | 12 | | SM00004 | | 9 | | 150-199 |
| 122 | 22 | | PA | | 3-11 | 33-21-34 | D01988 | | 12 | | SM00004 | | 9 | | 275-299 |
| 123 | 22 | | PA | | 13-0 | 33-21-34 | D02004 | | 2 | | D03154 | | 1 | | 050-099 |
| 123 | 22 | | PA | | 11-2 | 33-21-34 | D02004 | | 2 | | D03154 | | 1 | | 150-199, 275-299 |
| 124 | 22 | | PA | | 13-0 | 33-21-34 | D02004 | | 3 | | D03154 | | 2 | | 050-099 |
| 124 | 22 | | PA | | 11-2 | 33-21-34 | D02004 | | 3 | | D03154 | | 2 | | 150-199, 275-299 |
| 125 | 22 | | PA | | 9-0 | 33-21-34 | SM00005 | | 9 | | D03154 | | 3 | | 050-099 |
| 125 | 22 | | PA | | 8-5 | 33-21-34 | SM00005 | | 9 | | D03154 | | 3 | | 150-199, 275-299 |
| 126 | 22 | | PA | | 9-0 | 33-21-34 | SM00006 | | 9 | | D03154 | | 4 | | 050-099 |
| 126 | 22 | | PA | | 8-5 | 33-21-34 | SM00006 | | 9 | | D03154 | | 4 | | 150-199, 275-299 |
| 127 | 22 | | PA | | 8-0 | 33-21-34 | SM00005 | | 9 | | D03156 | | 3 | | 050-099 |
| 127 | 22 | | PA | | 9-4 | 33-21-34 | SM00034 | | 9 | | D03156 | | 3 | | 150-199, 275-299 |
| 128 | 22 | | PA | | 8-0 | 33-21-34 | SM00006 | | 9 | | D03156 | | 4 | | 050-099 |
| 128 | 22 | | PA | | 9-4 | 33-21-34 | SM00035 | | 9 | | D03156 | | 4 | | 150-199, 275-299 |
| 129 | 22 | | PA | | 11-0 | 33-21-34 | D02004 | | 9 | | D03156 | | 1 | | 050-099 |
| 129 | 22 | | PA | | 10-4 | 33-21-34 | D11234 | | 9 | | D03156 | | 1 | | 150-199, 275-299 |
| 130 | 22 | | PA | | 11-0 | 33-21-34 | D02004 | | 10 | | D03156 | | 2 | | 050-099 |
| 130 | 22 | | PA | | 10-4 | 33-21-34 | D11234 | | 10 | | D03156 | | 2 | | 150-199, 275-299 |
| 131 | 22 | | PA | | 5-0 | 33-21-34 | D02004 | | 11 | | SM00005 | | 9 | | 050-099 |
| 131 | 22 | | PA | | 4-2 | 33-21-34 | D02004 | | 11 | | SM00005 | | 9 | | 150-199, 275-299 |
| 132 | 22 | | PA | | 5-0 | 33-21-34 | D02004 | | 12 | | SM00006 | | 9 | | 050-099 |
| 132 | 22 | | PA | | 4-2 | 33-21-34 | D02004 | | 12 | | SM00006 | | 9 | | 150-199, 275-299 |
| 133 | 20 | | PA | | 8-0 | 33-21-34 | GD01580 | A.. | E | | D02006 | | 7 | | 050-099 |
| 133 | 20 | | PA | | 2-7 | 33-21-34 | GD01046 | A.. | E | | D02006 | | 7 | FM | 150-154, 157 |
| 133 | 20 | | PQ | G | 2-7 | 33-21-34 | GD01046 | A.. | E | | D02006 | | 7 | FM | 155-156 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 76

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | | |
| 133 | 20 | | PA | | 8-9 | 33-21-34 | GD01580 | A.. | E | | D02006 | 7 | FM | | 162-165, 167-199 | |
| 133 | 20 | | PQ | G | 8-9 | 33-21-34 | GD01580 | A.. | E | | D02006 | 7 | FM | | 166 | |
| 133 | 16 | | PA | | 2-7 | 33-21-34 | GD01046 | A.. | E | | D02006 | 7 | FM | | 275-299 | |
| 133Z | | | | G | 0-0 | 33-21-34 | GD01046 | DED | | | D02006 | DED | | | 155-156 | |
| 133Z | | | | G | 0-0 | 33-21-34 | GD01580 | DED | | | D02006 | DED | | | 166 | |
| 134 | 20 | | PA | | 8-0 | 33-21-34 | GD01578 | S.. | E | | D02006 | 8 | | | 050-099 | |
| 134 | 20 | | PA | | 2-7 | 33-21-34 | GD01572 | S.. | E | | D02006 | 8 | FM | | 150-157 | |
| 134 | 20 | | PA | | 8-9 | 33-21-34 | GD01578 | S.. | E | | D02006 | 8 | FM | | 162-199 | |
| 134 | 16 | | PA | | 2-7 | 33-21-34 | GD01572 | S.. | E | | D02006 | 8 | FM | | 275-299 | |
| 135 | 22 | | PA | | 13-0 | 33-21-34 | D03158 | | 1 | | D02006 | 9 | | | 050-099 | |
| 135 | 22 | | PA | | 10-11 | 33-21-34 | D03138 | | 1 | | D10050 | 9 | | | 150-157 | |
| 135 | 22 | | PA | | 34-7 | 33-21-34 | D10050 | | 9 | | D03138 | 1 | | | 162-199 | |
| 135 | 22 | | PA | | 10-11 | 33-21-34 | D03158 | | 1 | | D02006 | 2 | | | 275-299 | |
| 136 | 22 | | PA | | 7-0 | 33-21-34 | D03158 | | 2 | | D02006 | 10 | | | 050-099 | |
| 136 | 22 | | PA | | 10-11 | 33-21-34 | D03138 | | 2 | | D10050 | 10 | | | 150-157 | |
| 136 | 22 | | PA | | 34-7 | 33-21-34 | D10050 | | 10 | | D03138 | 2 | | | 162-199 | |
| 136 | 22 | | PA | | 10-11 | 33-21-34 | D03158 | | 2 | | D02006 | 3 | | | 275-299 | |
| 137 | 22 | | PA | | 7-0 | 33-21-34 | D03158 | | 3 | | D02006 | 11 | | | 050-099 | |
| 137 | 22 | | PA | | 6-9 | 33-21-34 | D03158 | | 3 | | D02006 | 11 | | | 150-157 | |
| 137 | 22 | | PA | | 11-3 | 33-21-34 | D03158 | | 3 | | D02006 | 11 | | | 162-199 | |
| 137 | 22 | | PA | | 6-9 | 33-21-34 | SM00026 | | 9 | | D02006 | 11 | | | 275-299 | |
| 138 | 22 | | PA | | 7-0 | 33-21-34 | D03158 | | 4 | | D02006 | 12 | | | 050-099 | |
| 138 | 22 | | PA | | 6-9 | 33-21-34 | D03158 | | 4 | | D02006 | 12 | | | 150-157 | |
| 138 | 22 | | PA | | 11-3 | 33-21-34 | D03158 | | 4 | | D02006 | 12 | | | 162-199 | |
| 138 | 22 | | PA | | 6-9 | 33-21-34 | SM00027 | | 9 | | D02006 | 12 | | | 275-299 | |
| 139 | 22 | | PA | | 12-0 | 33-21-34 | D01984 | | 5 | | SM00002 | | 9 | | 050-099 | |
| 139 | 20 | | PA | | 23-1 | 33-21-34 | D01984 | | 5 | | SM00002 | | 9 | | 150-154, 157-165, 167-199, 275-299 | |
| 139 | 20 | | PQ | FN | 23-1 | 33-21-34 | D01984 | | 5 | | SM00002 | | 9 | | 155-156, 166 | |
| 139Z | | | | FN | 0-0 | 33-21-34 | D01984 | DED | | | SM00002 | DED | | | 155-156, 166 | |
| 140 | 20 | | PA | | 4-0 | 33-21-34 | D01984 | | 8 | | GD01574 | S.. | E | | 050-099 | |
| 140 | 20 | | PA | | 2-11 | 33-21-34 | D01984 | | 8 | | GD01574 | S.. | E | | 150-199, 275-299 | |
| 141 | 20 | | PA | | 4-0 | 33-21-34 | D01984 | | 7 | | GD01042 | A.. | E | | 050-099 | |
| 141 | 20 | | PA | | 3-0 | 33-21-34 | D01984 | | 7 | | GD01042 | A.. | E | | 150-154, 157-165, 167-199, 275-299 | |
| 141 | 20 | | PQ | K | 3-0 | 33-21-34 | D01984 | | 7 | | GD01042 | A.. | E | | 155-156, 166 | |
| 141Z | | | | K | 0-0 | 33-21-34 | D01984 | DED | | | GD01042 | DED | | | 155-156, 166 | |
| 142 | 22 | | PA | | 13-0 | 33-21-34 | D01984 | | 2 | | D03160 | 1 | | | 050-099 | |
| 142 | 22 | | PA | | 12-6 | 33-21-34 | D01984 | | 2 | | D03160 | 1 | | | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 77

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | |
| 143 | 22 | | PA | 13-0 | 33-21-34 | D01984 | | 3 | | | D03160 | | 2 | | 050-099 |
| 143 | 22 | | PA | 12-6 | 33-21-34 | D01984 | | 3 | | | D03160 | | 2 | | 150-199, 275-299 |
| 144 | 22 | | PA | 10-0 | 33-21-34 | SM00007 | | | 9 | | D03160 | | 3 | | 050-099 |
| 144 | 22 | | PA | 9-1 | 33-21-34 | SM00007 | | | 9 | | D03160 | | 3 | | 150-199, 275-299 |
| 145 | 22 | | PA | 10-0 | 33-21-34 | SM00008 | | | 9 | | D03160 | | 4 | | 050-099 |
| 145 | 22 | | PA | 9-1 | 33-21-34 | SM00008 | | | 9 | | D03160 | | 4 | | 150-199, 275-299 |
| 146 | 22 | | PA | 8-0 | 33-21-34 | SM00007 | | | 9 | | D03162 | | 3 | | 050-099 |
| 146 | 22 | | PA | 8-2 | 33-21-34 | SM00007 | | | 9 | | D03162 | | 3 | | 150-199, 275-299 |
| 147 | 22 | | PA | 8-0 | 33-21-34 | SM00008 | | | 9 | | D03162 | | 4 | | 050-099 |
| 147 | 22 | | PA | 8-2 | 33-21-34 | SM00008 | | | 9 | | D03162 | | 4 | | 150-199, 275-299 |
| 148 | 22 | | PA | 10-0 | 33-21-34 | D01984 | | | 9 | | D03162 | | 1 | | 050-099 |
| 148 | 22 | | PA | 10-4 | 33-21-34 | D01984 | | | 9 | | D03162 | | 1 | | 150-199, 275-299 |
| 149 | 22 | | PA | 10-0 | 33-21-34 | D01984 | | | 10 | | D03162 | | 2 | | 050-099 |
| 149 | 22 | | PA | 10-4 | 33-21-34 | D01984 | | | 10 | | D03162 | | 2 | | 150-199, 275-299 |
| 150 | 22 | | PA | 5-0 | 33-21-34 | D01984 | | | 11 | | SM00007 | | | 9 | 050-099 |
| 150 | 22 | | PA | 3-11 | 33-21-34 | D01984 | | | 11 | | SM00007 | | | 9 | 150-199, 275-299 |
| 151 | 22 | | PA | 5-0 | 33-21-34 | D01984 | | | 12 | | SM00008 | | | 9 | 050-099 |
| 151 | 22 | | PA | 3-11 | 33-21-34 | D01984 | | | 12 | | SM00008 | | | 9 | 150-199, 275-299 |
| 152 | 22 | | PA | 21-0 | 33-21-34 | D01986 | | | 5 | | SM00002 | | | 9 | 050-099 |
| 152 | 20 | | PA | 30-4 | 33-21-34 | D01986 | | | 5 | | SM00002 | | | 9 | 150-154, 157-165, 167-199, 275-299 |
| 152 | 20 | | PQ | L | 30-4 | 33-21-34 | D01986 | | 5 | | SM00002 | | | 9 | 155-156, 166 |
| 152Z | | | | L | 0-0 | 33-21-34 | D01986 | | DED | | SM00002 | | DED | | 155-156, 166 |
| 153 | 20 | | PA | | 4-0 | 33-21-34 | D01986 | | 8 | | GD01578 | | S.. | E | 050-099 |
| 153 | 20 | | PA | | 2-7 | 33-21-34 | D01986 | | 8 | | GD01578 | | S.. | E | 150-199, 275-299 |
| 154 | 20 | | PA | | 4-0 | 33-21-34 | D01986 | | 7 | | GD01580 | | A.. | E | 050-099 |
| 154 | 20 | | PA | | 2-7 | 33-21-34 | D01986 | | 7 | | GD01580 | | A.. | E | 150-154, 157-165, 167-199, 275-299 |
| 154 | 20 | | PQ | M | 2-7 | 33-21-34 | D01986 | | 7 | | GD01580 | | A.. | E | 155-156, 166 |
| 154Z | | | | M | 0-0 | 33-21-34 | D01986 | | DED | | GD01580 | | DED | | 155-156, 166 |
| 155 | 22 | | PA | | 13-0 | 33-21-34 | D01986 | | 2 | | D03164 | | 1 | | 050-099 |
| 155 | 22 | | PA | | 12-1 | 33-21-34 | D01986 | | 2 | | D03164 | | 1 | | 150-199, 275-299 |
| 156 | 22 | | PA | | 13-0 | 33-21-34 | D01986 | | 3 | | D03164 | | 2 | | 050-099 |
| 156 | 22 | | PA | | 12-1 | 33-21-34 | D01986 | | 3 | | D03164 | | 2 | | 150-199, 275-299 |
| 157 | 22 | | PA | | 11-0 | 33-21-34 | SM00009 | | | 9 | D03164 | | 3 | | 050-099 |
| 157 | 22 | | PA | | 8-9 | 33-21-34 | SM00009 | | | 9 | D03164 | | 3 | | 150-199, 275-299 |
| 158 | 22 | | PA | | 11-0 | 33-21-34 | SM00010 | | | 9 | D03164 | | 4 | | 050-099 |
| 158 | 22 | | PA | | 8-9 | 33-21-34 | SM00010 | | | 9 | D03164 | | 4 | | 150-199, 275-299 |
| 159 | 22 | | PA | | 8-0 | 33-21-34 | SM00009 | | | 9 | D03166 | | 3 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 78

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 159 | 22 | | PA | 8-1 | 33-21-34 | SM00009 | | | | 9 | | | D03166 | 3 | | | 150-199, 275-299 |
| 160 | 22 | | PA | 8-0 | 33-21-34 | SM00010 | | | | 9 | | | D03166 | 4 | | | 050-099 |
| 160 | 22 | | PA | 8-1 | 33-21-34 | SM00010 | | | | 9 | | | D03166 | 4 | | | 150-199, 275-299 |
| 161 | 22 | | PA | 12-0 | 33-21-34 | D01986 | | | 9 | | | | D03166 | 1 | | | 050-099 |
| 161 | 22 | | PA | 10-4 | 33-21-34 | D01986 | | | 9 | | | | D03166 | 1 | | | 150-199, 275-299 |
| 162 | 22 | | PA | 12-0 | 33-21-34 | D01986 | | | 10 | | | | D03166 | 2 | | | 050-099 |
| 162 | 22 | | PA | 10-4 | 33-21-34 | D01986 | | | 10 | | | | D03166 | 2 | | | 150-199, 275-299 |
| 163 | 22 | | PA | 5-0 | 33-21-34 | D01986 | | | 11 | | | | SM00009 | | 9 | | 050-099 |
| 163 | 22 | | PA | 3-10 | 33-21-34 | D01986 | | | 11 | | | | SM00009 | | 9 | | 150-199, 275-299 |
| 164 | 22 | | PA | 5-0 | 33-21-34 | D01986 | | | 12 | | | | SM00010 | | 9 | | 050-099 |
| 164 | 22 | | PA | 3-10 | 33-21-34 | D01986 | | | 12 | | | | SM00010 | | 9 | | 150-199, 275-299 |
| 165 | 20 | | PA | 14-0 | 33-21-34 | GD02094 | | S.. | E | | | | D03150 | 5 | | | 050-099 |
| 165 | 20 | | PA | 10-2 | 33-21-34 | GD02094 | | S.. | E | | | | D03150 | 5 | | | 150-199, 275-299 |
| 166 | 20 | | PA | 3-0 | 33-21-34 | GD02068 | | S.. | E | | | | D03130 | 5 | | | 050-099 |
| 166 | 20 | | PA | 2-11 | 33-21-34 | GD02174 | | S.. | E | | | | D03152 | 5 | | | 150-199, 275-299 |
| 167 | 20 | | PA | 4-0 | 33-21-34 | GD02176 | | S.. | E | | | | D03154 | 5 | | | 050-099 |
| 167 | 20 | | PA | 3-1 | 33-21-34 | GD02176 | | S.. | E | | | | D03154 | 5 | | | 150-199, 275-299 |
| 168 | 20 | | PA | 4-0 | 33-21-34 | GD02178 | | S.. | E | | | | D03156 | 5 | | | 050-099 |
| 168 | 20 | | PA | 2-9 | 33-21-34 | GD04956 | | S.. | E | | | | D03156 | 5 | | | 150-199, 275-299 |
| 169 | 20 | | PA | 4-0 | 33-21-34 | GD02180 | | S.. | E | | | | D03158 | 5 | | | 050-099 |
| 169 | 20 | | PA | 2-11 | 33-21-34 | GD02180 | | S.. | E | | | | D03158 | 5 | | | 150-199, 275-299 |
| 170 | 20 | | PA | 4-0 | 33-21-34 | GD02182 | | S.. | E | | | | D03160 | 5 | | | 050-099 |
| 170 | 20 | | PA | 3-1 | 33-21-34 | GD02182 | | S.. | E | | | | D03160 | 5 | | | 150-199, 275-299 |
| 171 | 20 | | PA | 4-0 | 33-21-34 | GD02184 | | S.. | E | | | | D03162 | 5 | | | 050-099 |
| 171 | 20 | | PA | 3-0 | 33-21-34 | GD02184 | | S.. | E | | | | D03162 | 5 | | | 150-199, 275-299 |
| 172 | 20 | | PA | 4-0 | 33-21-34 | GD02186 | | S.. | E | | | | D03164 | 5 | | | 050-099 |
| 172 | 20 | | PA | 3-2 | 33-21-34 | GD02186 | | S.. | E | | | | D03164 | 5 | | | 150-199, 275-299 |
| 173 | 20 | | PA | 4-0 | 33-21-34 | GD02188 | | S.. | E | | | | D03166 | 5 | | | 050-099 |
| 173 | 20 | | PA | 2-10 | 33-21-34 | GD02188 | | S.. | E | | | | D03166 | 5 | | | 150-199, 275-299 |
| 500 | 20 | | PA | 19-9 | 33-21-34 | D05118P | | | | 1 | | | SM00031 | | 9 | | 150-154, 157-165, 167-199, 275-299 |
| 500 | 20 | | PQ | TY | 19-9 | 33-21-34 | D05118P | | | 1 | | | SM00031 | | 9 | | 155-156, 166 |
| 500Z | | | | TY | 0-0 | 33-21-34 | D05118P | | DED | | | | SM00031 | DED | | | 155-156, 166 |
| 577 | 22 | | PA | 8-10 | 33-21-34 | D03138 | | | | 3 | | | D10050 | 11 | | | 150-157 |
| 577 | 22 | | PA | 34-7 | 33-21-34 | D10050 | | | | 11 | | | D03138 | 3 | | | 162-199 |
| 577 | 22 | | PA | 8-10 | 33-21-34 | D03158 | | | | 3 | | | SM00026 | | 9 | | 275-299 |
| 578 | 22 | | PA | 8-10 | 33-21-34 | D03138 | | | | 4 | | | D10050 | 12 | | | 150-157 |
| 578 | 22 | | PA | 34-7 | 33-21-34 | D10050 | | | | 12 | | | D03138 | 4 | | | 162-199 |
| 578 | 22 | | PA | 8-10 | 33-21-34 | D03158 | | | | 4 | | | SM00027 | | 9 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 79

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | |
| 579 | 22 | | PA | 38-0 | 33-21-34 | D03138 | | 3 | | | D10050 | 11 | | | 050-099 |
| 579 | 22 | | PA | 15-11 | 33-21-34 | D03138 | | 3 | | | SM00026 | | 9 | | 275-299 |
| 580 | 22 | | PA | 38-0 | 33-21-34 | D03138 | | 4 | | | D10050 | 12 | | | 050-099 |
| 580 | 22 | | PA | 15-11 | 33-21-34 | D03138 | | 4 | | | SM00027 | | 9 | | 275-299 |
| 581 | 22 | | PA | 38-0 | 33-21-34 | D10050 | | 9 | | | D03138 | 1 | | | 050-099 |
| 581 | 22 | | PA | 21-8 | 33-21-34 | D02006 | | 9 | | | D03158 | 1 | | | 150-157 |
| 581 | 22 | | PA | 11-3 | 33-21-34 | D02006 | | 9 | | | D03158 | 1 | | | 162-199 |
| 581 | 22 | | PA | 21-8 | 33-21-34 | D02006 | | 9 | | | D03138 | 1 | | | 275-299 |
| 582 | 22 | | PA | 38-0 | 33-21-34 | D10050 | | 10 | | | D03138 | 2 | | | 050-099 |
| 582 | 22 | | PA | 21-8 | 33-21-34 | D02006 | | 10 | | | D03158 | 2 | | | 150-157 |
| 582 | 22 | | PA | 11-3 | 33-21-34 | D02006 | | 10 | | | D03158 | 2 | | | 162-199 |
| 582 | 22 | | PA | 21-8 | 33-21-34 | D02006 | | 10 | | | D03138 | 2 | | | 275-299 |
| 583 | 20 | | PA | 5-0 | 33-21-34 | D03138 | | 5 | | | GD03974 | S.. | E | | 050-099 |
| 583 | 20 | | PA | 3-9 | 33-21-34 | D03138 | | 5 | | | GD03974 | S.. | E | | 150-199, 275-299 |
| 584 | 20 | | PA | 11-9 | 33-21-34 | D11234 | | 5 | | | SM00031 | | 9 | | 150-154, 157-165, 167-199, 275-299 |
| 584 | 20 | | PQ | 11-9 | 33-21-34 | D11234 | | 5 | | | SM00031 | | 9 | | 155-156, 166 |
| 584Z | | | XI | 0-0 | 33-21-34 | D11234 | | DED | | | SM00031 | DED | | | 155-156, 166 |
| 585 | 22 | | PA | 28-0 | 33-21-14 | D00258 | | 2 | | | SP00954 | | 9 | | 050-099 |
| 585 | 20 | | PA | 24-6 | 33-21-14 | D00258 | | 2 | | | SP00954 | | 9 | | 150-199 |
| 585 | 20 | | PA | 20-10 | 33-21-14 | D00258 | | 2 | | | SP00954 | | 9 | | 275-299 |
| 586 | 22 | | PA | 27-0 | 33-21-14 | D00258 | | 3 | | | SP00956 | | 9 | | 050-099 |
| 586 | 20 | | PA | 24-6 | 33-21-14 | D00258 | | 3 | | | SP00956 | | 9 | | 150-199 |
| 586 | 20 | | PA | 20-10 | 33-21-14 | D00258 | | 3 | | | SP00956 | | 9 | | 275-299 |
| 587 | 20 | | PA | 8-0 | 33-21-14 | D00258 | | 5 | | | SM00028 | | 9 | | 050-099 |
| 587 | 20 | | PA | 9-7 | 33-21-14 | D00258 | | 5 | | | SM00028 | | 9 | | 150-199 |
| 587 | 20 | | PA | 5-4 | 33-21-14 | D00258 | | 5 | | | SM00028 | | 9 | | 275-299 |
| 588 | 20 | | PA | 5-0 | 33-21-14 | D00258 | | 7 | | | GD02788 | A.. | E | | 050-099 |
| 588 | 20 | | PA | 10-4 | 33-21-14 | D00258 | | 7 | | | GD04910 | A.. | E | | 150-199 |
| 588 | 20 | | PA | 6-8 | 33-21-14 | D00258 | | 7 | | | GD04910 | A.. | E | | 275-299 |
| 589 | 20 | | PA | 3-0 | 33-21-14 | D00258 | | 8 | | | GD02094 | S.. | E | | 050-099 |
| 589 | 20 | | PA | 10-4 | 33-21-14 | D00258 | | 8 | | | GD04914 | S.. | E | | 150-199 |
| 589 | 20 | | PA | 6-7 | 33-21-14 | D00258 | | 8 | | | GD04914 | S.. | E | | 275-299 |
| 590 | 22 | | PA | 17-0 | 33-21-14 | D00258 | | 9 | | | SP00962 | | 9 | | 050-099 |
| 590 | 20 | | PA | 12-5 | 33-21-14 | D00258 | | 9 | | | SP00962 | | 9 | | 150-199 |
| 590 | 20 | | PA | 15-10 | 33-21-14 | D00258 | | 9 | | | SP00962 | | 9 | | 275-299 |
| 591 | 22 | | PA | 17-0 | 33-21-14 | D00258 | | 10 | | | SP00964 | | 9 | | 050-099 |
| 591 | 20 | | PA | 12-5 | 33-21-14 | D00258 | | 10 | | | SP00964 | | 9 | | 150-199 |
| 591 | 20 | | PA | 15-10 | 33-21-14 | D00258 | | 10 | | | SP00964 | | 9 | | 275-299 |

WIRE LIST

D280T132

91-21-11
Section W0810
Page 80
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 592 | 22 | | PA | 15-0 | 33-21-14 | D00258 | | 11 | | | | | SP00966 | | 9 | | 050-099 |
| 592 | 20 | | PA | 9-1 | 33-21-14 | D00258 | | 11 | | | | | SP00966 | | 9 | | 150-199 |
| 592 | 20 | | PA | 9-7 | 33-21-14 | D00258 | | 11 | | | | | SP00966 | | 9 | | 275-299 |
| 593 | 22 | | PA | 15-0 | 33-21-14 | D00258 | | 12 | | | | | SP00968 | | 9 | | 050-099 |
| 593 | 20 | | PA | 9-1 | 33-21-14 | D00258 | | 12 | | | | | SP00968 | | 9 | | 150-199 |
| 593 | 20 | | PA | 9-7 | 33-21-14 | D00258 | | 12 | | | | | SP00968 | | 9 | | 275-299 |
| 594 | 20 | | PA | 18-0 | 33-21-14 | L00256 | | = G | E | | | | GD01564 | S.. | E | | 050-099 |
| 594 | 20 | | PA | 10-4 | 33-21-14 | L00256 | | = G | E | | | | GD04914 | S.. | E | | 150-199 |
| 594 | 20 | | PA | 8-1 | 33-21-14 | L00256 | | = G | E | | | | GD04914 | S.. | E | | 275-299 |
| 595 | 20 | | PA | 5-0 | 33-21-14 | L00257 | | = G | E | | | | GD01466 | S.. | E | | 050-099 |
| 595 | 20 | | PA | 4-11 | 33-21-14 | L00257 | | = G | E | | | | GD04920 | S.. | E | | 150-199, 275-299 |
| 596 | 22 | | PA | 30-0 | 33-21-14 | SP00958 | | | | 9 | | | SP00966 | | 9 | | 050-099 |
| 596 | 20 | | PA | 20-10 | 33-21-14 | SP00958 | | | | 9 | | | SP00966 | | 9 | | 150-199 |
| 596 | 20 | | PA | 25-0 | 33-21-14 | SP00958 | | | | 9 | | | SP00966 | | 9 | | 275-299 |
| 597 | 20 | | PA | 14-0 | 33-21-14 | SM00028 | | | | 9 | | | SM00029 | | 9 | | 050-099 |
| 597 | 20 | | PA | 11-2 | 33-21-14 | SM00028 | | | | 9 | | | SM00029 | | 9 | | 150-199, 275-299 |
| 598 | 22 | | PA | 30-0 | 33-21-14 | SP00960 | | | | 9 | | | SP00968 | | 9 | | 050-099 |
| 598 | 20 | | PA | 20-10 | 33-21-14 | SP00960 | | | | 9 | | | SP00968 | | 9 | | 150-199 |
| 598 | 20 | | PA | 25-0 | 33-21-14 | SP00960 | | | | 9 | | | SP00968 | | 9 | | 275-299 |
| 599 | 20 | | PA | 7-0 | 33-21-14 | D05118P | | | 4 | | | | SM00028 | | 9 | | 050-099 |
| 599 | 20 | | PA | 5-1 | 33-21-14 | D05118P | | | 4 | | | | SM00028 | | 9 | | 150-199, 275-299 |
| 600 | 22 | | PA | 30-0 | 33-21-14 | D00270 | | | 2 | | | | SP00970 | | 9 | | 050-099 |
| 600 | 20 | | PA | 18-11 | 33-21-14 | D00270 | | | 2 | | | | SP00970 | | 9 | | 150-199, 275-299 |
| 601 | 22 | | PA | 30-0 | 33-21-14 | D00270 | | | 3 | | | | SP00972 | | 9 | | 050-099 |
| 601 | 20 | | PA | 18-11 | 33-21-14 | D00270 | | | 3 | | | | SP00972 | | 9 | | 150-199, 275-299 |
| 602 | 20 | | PA | 6-0 | 33-21-14 | D00270 | | | 5 | | | | SM00029 | | 9 | | 050-099 |
| 602 | 20 | | PA | 7-9 | 33-21-14 | D00270 | | | 5 | | | | SM00029 | | 9 | | 150-199, 275-299 |
| 603 | 20 | | PA | 5-0 | 33-21-14 | D00270 | | | 7 | | | | GD02808 | A.. | E | | 050-099 |
| 603 | 20 | | PA | 3-1 | 33-21-14 | D00270 | | | 7 | | | | GD04878 | A.. | E | | 150-199, 275-299 |
| 604 | 20 | | PA | 4-0 | 33-21-14 | D00270 | | | 8 | | | | GD04716 | S.. | E | | 050-099 |
| 604 | 20 | | PA | 3-4 | 33-21-14 | D00270 | | | 8 | | | | GD04880 | S.. | E | | 150-199, 275-299 |
| 605 | 22 | | PA | 24-0 | 33-21-14 | D00270 | | | 9 | | | | SP00978 | | 9 | | 050-099 |
| 605 | 20 | | PA | 13-7 | 33-21-14 | D00270 | | | 9 | | | | SP00978 | | 9 | | 150-199, 275-299 |
| 606 | 22 | | PA | 24-0 | 33-21-14 | D00270 | | | 10 | | | | SP00980 | | 9 | | 050-099 |
| 606 | 20 | | PA | 13-7 | 33-21-14 | D00270 | | | 10 | | | | SP00980 | | 9 | | 150-199, 275-299 |
| 607 | 22 | | PA | 13-0 | 33-21-14 | D00270 | | | 11 | | | | SP00982 | | 9 | | 050-099 |
| 607 | 20 | | PA | 9-6 | 33-21-14 | D00270 | | | 11 | | | | SP00982 | | 9 | | 150-199, 275-299 |
| 608 | 22 | | PA | 13-0 | 33-21-14 | D00270 | | | 12 | | | | SP00984 | | 9 | | 050-099 |
| 608 | 20 | | PA | 9-6 | 33-21-14 | D00270 | | | 12 | | | | SP00984 | | 9 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 81

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | |
| 609 | 20 | | PA | | 8-0 | 33-21-14 | L00258 | =G | E | | GD01568 | S.. | E | | 050-099 |
| 609 | 20 | | PA | | 6-4 | 33-21-14 | L00258 | =G | E | | GD04886 | S.. | E | | 150-199, 275-299 |
| 610 | 20 | | PA | | 4-0 | 33-21-14 | L00259 | =G | E | | GD01474 | S.. | E | | 050-099 |
| 610 | 20 | | PA | | 9-1 | 33-21-14 | L00259 | =G | E | | GD04892 | S.. | E | | 150-199, 275-299 |
| 611 | 22 | | PA | | 30-0 | 33-21-14 | SP00974 | | 9 | | SP00982 | | 9 | | 050-099 |
| 611 | 20 | | PA | | 30-2 | 33-21-14 | SP00974 | | 9 | | SP00982 | | 9 | | 150-199, 275-299 |
| 612 | 22 | | PA | | 30-0 | 33-21-14 | SP00976 | | 9 | | SP00984 | | 9 | | 050-099 |
| 612 | 20 | | PA | | 30-2 | 33-21-14 | SP00976 | | 9 | | SP00984 | | 9 | | 150-199, 275-299 |
| 613 | 22 | | PA | | 32-0 | 33-21-14 | D00276 | | 2 | | SP00986 | | 9 | | 050-099 |
| 613 | 20 | | PA | | 22-1 | 33-21-14 | D00276 | | 2 | | SP00986 | | 9 | | 150-199, 275-299 |
| 614 | 22 | | PA | | 32-0 | 33-21-14 | D00276 | | 3 | | SP00988 | | 9 | | 050-099 |
| 614 | 20 | | PA | | 22-1 | 33-21-14 | D00276 | | 3 | | SP00988 | | 9 | | 150-199, 275-299 |
| 615 | 20 | | PA | | 11-0 | 33-21-14 | D00276 | | 5 | | SM00029 | | 9 | | 050-099 |
| 615 | 20 | | PA | | 22-7 | 33-21-14 | D00276 | | 5 | | SM00029 | | 9 | | 150-199, 275-299 |
| 616 | 20 | | PA | | 5-0 | 33-21-14 | D00276 | | 7 | | GD02814 | A.. | E | | 050-099 |
| 616 | 20 | | PA | | 3-8 | 33-21-14 | D00276 | | 7 | | GD02814 | A.. | E | | 150-199, 275-299 |
| 617 | 20 | | PA | | 4-0 | 33-21-14 | D00276 | | 8 | | GD04718 | S.. | E | | 050-099 |
| 617 | 20 | | PA | | 3-9 | 33-21-14 | D00276 | | 8 | | GD04718 | S.. | E | | 150-199, 275-299 |
| 618 | 22 | | PA | | 18-0 | 33-21-14 | D00276 | | 9 | | SP00994 | | 9 | | 050-099 |
| 618 | 20 | | PA | | 11-7 | 33-21-14 | D00276 | | 9 | | SP00994 | | 9 | | 150-199, 275-299 |
| 619 | 22 | | PA | | 18-0 | 33-21-14 | D00276 | | 10 | | SP00996 | | 9 | | 050-099 |
| 619 | 20 | | PA | | 11-7 | 33-21-14 | D00276 | | 10 | | SP00996 | | 9 | | 150-199, 275-299 |
| 620 | 22 | | PA | | 14-0 | 33-21-14 | D00276 | | 11 | | SP00998 | | 9 | | 050-099 |
| 620 | 20 | | PA | | 8-10 | 33-21-14 | D00276 | | 11 | | SP00998 | | 9 | | 150-199, 275-299 |
| 621 | 22 | | PA | | 14-0 | 33-21-14 | D00276 | | 12 | | SP01000 | | 9 | | 050-099 |
| 621 | 20 | | PA | | 8-10 | 33-21-14 | D00276 | | 12 | | SP01000 | | 9 | | 150-199, 275-299 |
| 622 | 20 | | PA | | 20-0 | 33-21-14 | L00260 | =G | E | | GD01568 | S.. | E | | 050-099 |
| 622 | 20 | | PA | | 4-9 | 33-21-14 | L00260 | =G | E | | GD01574 | S.. | E | | 150-199, 275-299 |
| 623 | 20 | | PA | | 7-0 | 33-21-14 | L00261 | =G | E | | GD01478 | S.. | E | | 050-099 |
| 623 | 20 | | PA | | 11-6 | 33-21-14 | L00261 | =G | E | | GD04898 | S.. | E | | 150-199, 275-299 |
| 624 | 22 | | PA | | 31-0 | 33-21-14 | SP00990 | | 9 | | SP00998 | | 9 | | 050-099 |
| 624 | 20 | | PA | | 27-9 | 33-21-14 | SP00990 | | 9 | | SP00998 | | 9 | | 150-199, 275-299 |
| 625 | 22 | | PA | | 31-0 | 33-21-14 | SP00992 | | 9 | | SP01000 | | 9 | | 050-099 |
| 625 | 20 | | PA | | 27-9 | 33-21-14 | SP00992 | | 9 | | SP01000 | | 9 | | 150-199, 275-299 |
| 626 | 22 | | PA | | 34-0 | 33-21-14 | D00296 | | 2 | | SP01002 | | 9 | | 050-099 |
| 626 | 20 | | PA | | 21-3 | 33-21-14 | D00296 | | 2 | | SP01002 | | 9 | | 150-199, 275-299 |
| 627 | 22 | | PA | | 34-0 | 33-21-14 | D00296 | | 3 | | SP01004 | | 9 | | 050-099 |
| 627 | 20 | | PA | | 21-3 | 33-21-14 | D00296 | | 3 | | SP01004 | | 9 | | 150-199, 275-299 |
| 628 | 20 | | PA | | 6-0 | 33-21-14 | D00296 | | 5 | | SM00030 | | 9 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 82
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 628 | 20 | | PA | | 4-0 | 33-21-14 | D00296 | | 5 | | | | SM00030 | | 9 | | 150-199 |
| 628 | 20 | | PA | | 44-1 | 33-21-14 | D00296 | | 5 | | | | D05118P | | 6 | | 275-299 |
| 629 | 20 | | PA | | 6-2 | 33-21-14 | L00772 | | =G | E | | | GD04942 | S.. | E | | 150-199, 275-299 |
| 630 | 20 | | PA | | 5-0 | 33-21-14 | D00296 | | 7 | | | | GD02848 | A.. | E | | 050-099 |
| 630 | 20 | | PA | | 3-7 | 33-21-14 | D00296 | | 7 | | | | GD02848 | A.. | E | | 150-199, 275-299 |
| 631 | 20 | | PA | | 4-3 | 33-21-34 | D11232 | | 5 | | | | SM00031 | | 9 | | 150-154, 157-165, 167-199, 275-299 |
| 631 | 20 | | PQ | ZF | 4-3 | 33-21-34 | D11232 | | 5 | | | | SM00031 | | 9 | | 155-156, 166 |
| 631Z | | | | ZF | 0-0 | 33-21-34 | D11232 | | DED | | | | SM00031 | DED | | | 155-156, 166 |
| 632 | 20 | | PA | | 4-0 | 33-21-14 | D00296 | | 8 | | | | GD04720 | S.. | E | | 050-099 |
| 632 | 20 | | PA | | 3-7 | 33-21-14 | D00296 | | 8 | | | | GD04720 | S.. | E | | 150-199, 275-299 |
| 633 | 22 | | PA | | 18-0 | 33-21-14 | D00296 | | 9 | | | | SP01010 | | 9 | | 050-099 |
| 633 | 20 | | PA | | 12-7 | 33-21-14 | D00296 | | 9 | | | | SP01010 | | 9 | | 150-199, 275-299 |
| 634 | 22 | | PA | | 18-0 | 33-21-14 | D00296 | | 10 | | | | SP01012 | | 9 | | 050-099 |
| 634 | 20 | | PA | | 12-7 | 33-21-14 | D00296 | | 10 | | | | SP01012 | | 9 | | 150-199, 275-299 |
| 635 | 22 | | PA | | 13-0 | 33-21-14 | D00296 | | 11 | | | | SP01014 | | 9 | | 050-099 |
| 635 | 20 | | PA | | 8-2 | 33-21-14 | D00296 | | 11 | | | | SP01014 | | 9 | | 150-199, 275-299 |
| 636 | 22 | | PA | | 13-0 | 33-21-14 | D00296 | | 12 | | | | SP01016 | | 9 | | 050-099 |
| 636 | 20 | | PA | | 8-2 | 33-21-14 | D00296 | | 12 | | | | SP01016 | | 9 | | 150-199, 275-299 |
| 637 | 20 | | PA | | 18-0 | 33-21-14 | L00274 | | =G | E | | | GD01578 | S.. | E | | 050-099 |
| 637 | 20 | | PA | | 4-11 | 33-21-14 | L00274 | | =G | E | | | GD01578 | S.. | E | | 150-199, 275-299 |
| 638 | 20 | | PA | | 6-0 | 33-21-14 | L00275 | | =G | E | | | GD01486 | S.. | E | | 050-099 |
| 638 | 20 | | PA | | 5-3 | 33-21-14 | L00275 | | =G | E | | | GD01486 | S.. | E | | 150-199, 275-299 |
| 639 | 22 | | PA | | 30-0 | 33-21-14 | SP01006 | | | 9 | | | SP01014 | | 9 | | 050-099 |
| 639 | 20 | | PA | | 24-7 | 33-21-14 | SP01006 | | | 9 | | | SP01014 | | 9 | | 150-199, 275-299 |
| 640 | 22 | | PA | | 30-0 | 33-21-14 | SP01008 | | | 9 | | | SP01016 | | 9 | | 050-099 |
| 640 | 20 | | PA | | 24-7 | 33-21-14 | SP01008 | | | 9 | | | SP01016 | | 9 | | 150-199, 275-299 |
| 641 | 22 | | PA | | 25-0 | 33-21-14 | D00318 | | | 2 | | | SP01018 | | 9 | | 050-099 |
| 641 | 20 | | PA | | 19-0 | 33-21-14 | D00318 | | | 2 | | | SP01018 | | 9 | | 150-157, 275-299 |
| 641 | 20 | | PA | | 23-0 | 33-21-14 | D00318 | | | 2 | | | SP01018 | | 9 | | 162-199 |
| 642 | 22 | | PA | | 25-0 | 33-21-14 | D00318 | | | 3 | | | SP01020 | | 9 | | 050-099 |
| 642 | 20 | | PA | | 19-0 | 33-21-14 | D00318 | | | 3 | | | SP01020 | | 9 | | 150-157, 275-299 |
| 642 | 20 | | PA | | 23-0 | 33-21-14 | D00318 | | | 3 | | | SP01020 | | 9 | | 162-199 |
| 643 | 20 | | PA | | 5-0 | 33-21-14 | D00318 | | | 5 | | | SM00030 | | 9 | | 050-099 |
| 643 | 20 | | PA | | 8-7 | 33-21-14 | D00318 | | | 5 | | | SM00030 | | 9 | | 150-157 |
| 643 | 20 | | PA | | 4-7 | 33-21-14 | D00318 | | | 5 | | | SM00030 | | 9 | | 162-199 |
| 643 | 20 | | PA | | 49-3 | 33-21-14 | D00318 | | | 5 | | | D05118P | | 2 | | 275-299 |
| 644 | 20 | | PA | | 7-0 | 33-21-14 | D00318 | | | 7 | | | GD01580 | A.. | E | | 050-099 |
| 644 | 20 | | PA | | 6-10 | 33-21-14 | D00318 | | | 7 | | | GD01046 | A.. | E | | 150-157, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 83

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| 644 | 20 | | PA | | 10-11 | 33-21-14 | D00318 | | 7 | | | | GD01046 | A.. | E | | 162-199 |
| 645 | 20 | | PA | | 7-0 | 33-21-14 | D00318 | | 8 | | | | GD01578 | S.. | E | | 050-099 |
| 645 | 20 | | PA | | 6-11 | 33-21-14 | D00318 | | 8 | | | | GD01572 | S.. | E | | 150-157, 275-299 |
| 645 | 20 | | PA | | 10-11 | 33-21-14 | D00318 | | 8 | | | | GD01572 | S.. | E | | 162-199 |
| 646 | 22 | | PA | | 7-0 | 33-21-14 | D00318 | | 9 | | | | SP01026 | | 9 | | 050-099 |
| 646 | 20 | | PA | | 10-8 | 33-21-14 | D00318 | | 9 | | | | SP01026 | | 9 | | 150-157, 275-299 |
| 646 | 20 | | PA | | 4-2 | 33-21-14 | D00318 | | 9 | | | | SP01026 | | 9 | | 162-199 |
| 647 | 22 | | PA | | 7-0 | 33-21-14 | D00318 | | 10 | | | | SP01028 | | 9 | | 050-099 |
| 647 | 20 | | PA | | 10-8 | 33-21-14 | D00318 | | 10 | | | | SP01028 | | 9 | | 150-157, 275-299 |
| 647 | 20 | | PA | | 4-2 | 33-21-14 | D00318 | | 10 | | | | SP01028 | | 9 | | 162-199 |
| 648 | 22 | | PA | | 15-0 | 33-21-14 | D00318 | | 11 | | | | SP01030 | | 9 | | 050-099 |
| 648 | 20 | | PA | | 9-6 | 33-21-14 | D00318 | | 11 | | | | SP01030 | | 9 | | 150-157, 275-299 |
| 648 | 20 | | PA | | 13-7 | 33-21-14 | D00318 | | 11 | | | | SP01030 | | 9 | | 162-199 |
| 649 | 22 | | PA | | 15-0 | 33-21-14 | D00318 | | 12 | | | | SP01032 | | 9 | | 050-099 |
| 649 | 20 | | PA | | 9-6 | 33-21-14 | D00318 | | 12 | | | | SP01032 | | 9 | | 150-157, 275-299 |
| 649 | 20 | | PA | | 13-7 | 33-21-14 | D00318 | | 12 | | | | SP01032 | | 9 | | 162-199 |
| 650 | 20 | | PA | | 14-0 | 33-21-14 | L00278 | | =G | E | | | GD01572 | S.. | E | | 050-099 |
| 650 | 20 | | PA | | 4-7 | 33-21-14 | L00278 | | =G | E | | | GD01572 | S.. | E | | 150-199, 275-299 |
| 651 | 20 | | PA | | 8-0 | 33-21-14 | L00279 | | =G | E | | | GD01530 | S.. | E | | 050-099 |
| 651 | 20 | | PA | | 6-7 | 33-21-14 | L00279 | | =G | E | | | GD01530 | S.. | E | | 150-199, 275-299 |
| 652 | 22 | | PA | | 28-0 | 33-21-14 | SP01022 | | | 9 | | | SP01030 | | 9 | | 050-099 |
| 652 | 20 | | PA | | 25-7 | 33-21-14 | SP01022 | | | 9 | | | SP01030 | | 9 | | 150-199, 275-299 |
| 653 | 22 | | PA | | 28-0 | 33-21-14 | SP01024 | | | 9 | | | SP01032 | | 9 | | 050-099 |
| 653 | 20 | | PA | | 25-7 | 33-21-14 | SP01024 | | | 9 | | | SP01032 | | 9 | | 150-199, 275-299 |
| 654 | 20 | | PA | | 32-0 | 33-21-14 | D05118P | | | 6 | | | SM00030 | | 9 | | 050-099 |
| 654 | 20 | | PA | | 41-8 | 33-21-14 | D05118P | | | 6 | | | SM00030 | | 9 | | 150-199 |
| 655 | 22 | | PA | | 47-0 | 33-21-34 | D10050 | | | 5 | | | D05118P | | 12 | | 050-099 |
| 655 | 22 | | PA | | 56-6 | 33-21-34 | D10050 | | | 5 | | | D05118P | | 12 | | 150-165, 167-199 |
| 655 | 22 | | PQ | A5 | 56-6 | 33-21-34 | D10050 | | | 5 | | | D05118P | | 12 | | 166 |
| 655Z | | | | A5 | 0-0 | 33-21-34 | D10050 | | DED | | | | D05118P | DED | | | 166 |
| 656 | 20 | | PA | | 8-0 | 33-21-34 | D10050 | | | 7 | | | GD01528 | A.. | E | | 050-099 |
| 656 | 20 | | PA | | 4-3 | 33-21-34 | D10050 | | | 7 | | | GD01528 | A.. | E | | 150-165, 167-199 |
| 656 | 20 | | PQ | A6 | 4-3 | 33-21-34 | D10050 | | | 7 | | | GD01528 | A.. | E | | 166 |
| 656Z | | | | A6 | 0-0 | 33-21-34 | D10050 | | DED | | | | GD01528 | DED | | | 166 |
| 657 | 20 | | PA | | 8-0 | 33-21-34 | D10050 | | | 8 | | | GD01530 | S.. | E | | 050-099 |
| 657 | 20 | | PA | | 4-3 | 33-21-34 | D10050 | | | 8 | | | GD01530 | S.. | E | | 150-199 |
| 662 | 20 | | PA | | 20-11 | 33-21-14 | D11212 | | | 2 | | | SP02950 | | 9 | | 150-199, 275-299 |
| 663 | 20 | | PA | | 20-11 | 33-21-14 | D11212 | | | 3 | | | SP02952 | | 9 | | 150-199, 275-299 |
| 664 | 20 | | PA | | 13-11 | 33-21-14 | D11212 | | | 9 | | | SP02958 | | 9 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 84

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---------------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | | |
| 665 | 20 | PA | | 13-11 | 33-21-14 | D11212 | 10 | | | | | | SP02960 | | 9 | 150-199, 275-299 |
| 666 | 20 | PA | | 8-9 | 33-21-14 | D11212 | 12 | | | | | | SP02964 | | 9 | 150-199, 275-299 |
| 667 | 20 | PA | | 8-9 | 33-21-14 | D11212 | 11 | | | | | | SP02962 | | 9 | 150-199, 275-299 |
| 668 | 20 | PA | | 3-0 | 33-21-14 | D11212 | 7 | | | | | | GD04900 | A.. | E | 150-199, 275-299 |
| 669 | 20 | PA | | 3-0 | 33-21-14 | D11212 | 8 | | | | | | GD04902 | S.. | E | 150-199, 275-299 |
| 670 | 20 | PA | | 27-6 | 33-21-14 | SP02954 | | | | 9 | | | SP02962 | | 9 | 150-199, 275-299 |
| 671 | 20 | PA | | 27-6 | 33-21-14 | SP02956 | | | | 9 | | | SP02964 | | 9 | 150-199, 275-299 |
| 672 | 20 | PA | | 19-10 | 33-21-14 | D11216 | 2 | | | | | | SP02974 | | 9 | 150-199, 275-299 |
| 673 | 20 | PA | | 19-10 | 33-21-14 | D11216 | 3 | | | | | | SP02976 | | 9 | 150-199, 275-299 |
| 674 | 20 | PA | | 12-7 | 33-21-14 | D11216 | 9 | | | | | | SP02966 | | 9 | 150-199, 275-299 |
| 675 | 20 | PA | | 12-7 | 33-21-14 | D11216 | 10 | | | | | | SP02968 | | 9 | 150-199, 275-299 |
| 676 | 20 | PA | | 8-7 | 33-21-14 | D11216 | 12 | | | | | | SP02972 | | 9 | 150-199, 275-299 |
| 677 | 20 | PA | | 8-7 | 33-21-14 | D11216 | 11 | | | | | | SP02970 | | 9 | 150-199, 275-299 |
| 678 | 20 | PA | | 3-8 | 33-21-14 | D11216 | 7 | | | | | | GD04934 | A.. | E | 150-199, 275-299 |
| 679 | 20 | PA | | 3-10 | 33-21-14 | D11216 | 8 | | | | | | GD04936 | S.. | E | 150-199, 275-299 |
| 681 | 22 | PA | | 11-5 | 33-21-34 | D01988 | 9 | | | | | | D03094 | 1 | | 150-199 |
| 681 | 22 | PA | | 12-5 | 33-21-34 | D01988 | 9 | | | | | | D03094 | 1 | | 275-299 |
| 682 | 22 | PA | | 11-5 | 33-21-34 | D01988 | 10 | | | | | | D03094 | 2 | | 150-199 |
| 682 | 22 | PA | | 12-5 | 33-21-34 | D01988 | 10 | | | | | | D03094 | 2 | | 275-299 |
| 683 | 22 | PA | | 9-8 | 33-21-34 | SM00003 | | | | 9 | | | D03094 | 3 | | 150-199, 275-299 |
| 684 | 22 | PA | | 9-8 | 33-21-34 | SM00004 | | | | 9 | | | D03094 | 4 | | 150-199, 275-299 |
| 685 | 20 | PA | | 2-8 | 33-21-34 | GD02090 | | S.. | E | | | | D03094 | 5 | | 150-199, 275-299 |
| 686 | 20 | PA | | 3-9 | 33-21-34 | D11232 | 8 | | | | | | GD04926 | S.. | E | 150-199, 275-299 |
| 687 | 20 | PA | | 3-10 | 33-21-34 | D11232 | 7 | | | | | | GD04922 | A.. | E | 150-154, 157-165, 167-199, 275-299 |
| 687 | 20 | PQ | D7 | 3-10 | 33-21-34 | D11232 | 7 | | | | | | GD04922 | A.. | E | 155-156, 166 |
| 687Z | | | D7 | 0-0 | 33-21-34 | D11232 | | DED | | | | | GD04922 | DED | | 155-156, 166 |
| 688 | 22 | PA | | 12-9 | 33-21-34 | D11232 | 2 | | | | | | D11236 | 1 | | 150-199, 275-299 |
| 689 | 22 | PA | | 12-9 | 33-21-34 | D11232 | 3 | | | | | | D11236 | 2 | | 150-199, 275-299 |
| 690 | 22 | PA | | 9-1 | 33-21-34 | D11236 | 3 | | | | | | SM00032 | 9 | | 150-199, 275-299 |
| 691 | 22 | PA | | 9-1 | 33-21-34 | D11236 | 4 | | | | | | SM00033 | 9 | | 150-199, 275-299 |
| 692 | 20 | PA | | 2-8 | 33-21-34 | GD02178 | | S.. | E | | | | D11236 | 5 | | 150-199, 275-299 |
| 693 | 22 | PA | | 8-1 | 33-21-34 | D11238 | 3 | | | | | | SM00032 | 9 | | 150-199, 275-299 |
| 694 | 22 | PA | | 8-1 | 33-21-34 | D11238 | 4 | | | | | | SM00033 | 9 | | 150-199, 275-299 |
| 695 | 22 | PA | | 10-7 | 33-21-34 | D11232 | 9 | | | | | | D11238 | 1 | | 150-199, 275-299 |
| 696 | 22 | PA | | 10-7 | 33-21-34 | D11232 | 10 | | | | | | D11238 | 2 | | 150-199, 275-299 |
| 697 | 20 | PA | | 2-11 | 33-21-34 | GD04952 | | S.. | E | | | | D11238 | 5 | | 150-199, 275-299 |
| 698 | 22 | PA | | 4-3 | 33-21-34 | D11232 | 11 | | | | | | SM00032 | 9 | | 150-199, 275-299 |
| 699 | 22 | PA | | 4-3 | 33-21-34 | D11232 | 12 | | | | | | SM00033 | 9 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 85

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | |
| 700 | 20 | PA | | 3-9 | 33-21-34 | D11234 | | 8 | | | GD04942 | S.. | E | | 150-199, 275-299 |
| 701 | 20 | PA | | 3-9 | 33-21-34 | D11234 | | 7 | | | GD04938 | A.. | E | | 150-154, 157-165, 167-199, 275-299 |
| 701 | 20 | PQ | G1 | 3-9 | 33-21-34 | D11234 | | 7 | | | GD04938 | A.. | E | | 155-156, 166 |
| 701Z | | | G1 | 0-0 | 33-21-34 | D11234 | | DED | | | GD04938 | DED | | | 155-156, 166 |
| 702 | 22 | PA | | 12-6 | 33-21-34 | D11234 | | 2 | | | D11240 | | 1 | | 150-199, 275-299 |
| 703 | 22 | PA | | 12-6 | 33-21-34 | D11234 | | 3 | | | D11240 | | 2 | | 150-199, 275-299 |
| 704 | 22 | PA | | 7-10 | 33-21-34 | D11240 | | 3 | | | SM00034 | | | 9 | 150-199, 275-299 |
| 705 | 22 | PA | | 7-10 | 33-21-34 | D11240 | | 4 | | | SM00035 | | | 9 | 150-199, 275-299 |
| 706 | 20 | PA | | 2-11 | 33-21-34 | GD04954 | | S.. | E | | D11240 | | 5 | | 150-199, 275-299 |
| 707 | 22 | PA | | 5-3 | 33-21-34 | D11234 | | 11 | | | SM00034 | | | 9 | 150-199, 275-299 |
| 708 | 22 | PA | | 5-3 | 33-21-34 | D11234 | | 12 | | | SM00035 | | | 9 | 150-199, 275-299 |
| 800 | 18 | PA | | 12-2 | 33-27-11 | L01139 | | =G | C | | GD00070 | A.. | 2 | | 150-199 |
| 801 | 18 | PA | | 77-10 | 33-27-11 | L01139 | | =P | C | | D05118P | | 7 | | 150-157 |
| 801 | 18 | PA | | 77-10 | 33-27-11 | L01139 | | =P | C | * | D05118P | | 7 | | 162-199 |
| 802 | 18 | PA | | 7-11 | 33-27-11 | L01139 | | =P | C | | L01141 | =P | C | | 150-157 |
| 802 | 18 | PA | | 7-11 | 33-27-11 | L01139 | | =P | C | * | L01141 | =P | C | | 162-199 |
| 803 | 18 | PA | | 14-0 | 33-27-11 | L01141 | | =G | C | | GD00932 | A.. | 2 | | 150-199 |
| A-A | | | | 0-0 | 33-27-11 | L00208 | | BLK | | | SP01286 | | 9 | | ALL |
| A-B | | | | 0-0 | 33-27-11 | L00208 | | BLK | | | SP01288 | | 9 | | ALL |
| A-C | | | | 0-0 | 33-27-11 | L00208 | | WHT | | | SP01320 | | 9 | | ALL |
| A-D | | | | 0-0 | 33-27-11 | L00208 | | WHT | | | SP01318 | | 9 | | ALL |
| A-E | | | | 0-0 | 33-21-14 | L00769 | | BLK | | | SP02950 | | 9 | | 150-199, 275-299 |
| A-F | | | | 0-0 | 33-21-14 | L00769 | | BLK | | | SP02952 | | 9 | | 150-199, 275-299 |
| A-G | | | | 0-0 | 33-21-14 | L00769 | | WHT | | | SP02954 | | 9 | | 150-199, 275-299 |
| A-H | | | | 0-0 | 33-21-14 | L00769 | | WHT | | | SP02956 | | 9 | | 150-199, 275-299 |
| A-J | | | | 0-0 | 33-21-14 | L00768 | | BLK | | | SP02958 | | 9 | | 150-199, 275-299 |
| A-K | | | | 0-0 | 33-21-14 | L00768 | | BLK | | | SP02960 | | 9 | | 150-199, 275-299 |
| A-L | | | | 0-0 | 33-21-14 | L00768 | | WHT | | | SP02962 | | 9 | | 150-199, 275-299 |
| A-M | | | | 0-0 | 33-21-14 | L00768 | | WHT | | | SP02964 | | 9 | | 150-199, 275-299 |
| A-P | | | | 0-0 | 33-21-14 | L00772 | | BLK | | | SP02966 | | 9 | | 150-199, 275-299 |
| A-R | | | | 0-0 | 33-21-14 | L00772 | | BLK | | | SP02968 | | 9 | | 150-199, 275-299 |
| A-S | | | | 0-0 | 33-21-14 | L00772 | | WHT | | | SP02972 | | 9 | | 150-199, 275-299 |
| A-T | | | | 0-0 | 33-21-14 | L00772 | | WHT | | | SP02970 | | 9 | | 150-199, 275-299 |
| A-U | | | | 0-0 | 33-21-14 | L00773 | | BLK | | | SP02974 | | 9 | | 150-199, 275-299 |
| A-V | | | | 0-0 | 33-21-14 | L00773 | | BLK | | | SP02976 | | 9 | | 150-199, 275-299 |
| A-W | | | | 0-0 | 33-21-14 | L00773 | | WHT | | | SP02978 | | 9 | | 150-199, 275-299 |
| A-X | | | | 0-0 | 33-21-14 | L00773 | | WHT | | | SP02980 | | 9 | | 150-199, 275-299 |
| B-A | | | | 0-0 | 33-27-11 | L00204 | | BLK | | | SP01292 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 86

Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|-----|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | | | |
| B-B | | | | | 0-0 | 33-27-11 | L00204 | | BLK | | | | SP01290 | | 9 | | ALL |
| B-C | | | | | 0-0 | 33-27-11 | L00204 | | WHT | | | | SP01272 | | 9 | | ALL |
| B-D | | | | | 0-0 | 33-27-11 | L00204 | | WHT | | | | SP01270 | | 9 | | ALL |
| C-A | | | | | 0-0 | 33-27-11 | L00207 | | BLK | | | | SP01298 | | 9 | | ALL |
| C-B | | | | | 0-0 | 33-27-11 | L00207 | | BLK | | | | SP01300 | | 9 | | ALL |
| C-C | | | | | 0-0 | 33-27-11 | L00207 | | WHT | | | | SP01302 | | 9 | | ALL |
| C-D | | | | | 0-0 | 33-27-11 | L00207 | | WHT | | | | SP01304 | | 9 | | ALL |
| D-A | | | | | 0-0 | 33-27-11 | L00203 | | BLK | | | | SP01306 | | 9 | | ALL |
| D-B | | | | | 0-0 | 33-27-11 | L00203 | | BLK | | | | SP01308 | | 9 | | ALL |
| D-C | | | | | 0-0 | 33-27-11 | L00203 | | WHT | | | | SP01310 | | 9 | | ALL |
| D-D | | | | | 0-0 | 33-27-11 | L00203 | | WHT | | | | SP01312 | | 9 | | ALL |
| E-A | | | | | 0-0 | 33-21-14 | L00256 | | BLK | | | | SP00962 | | 9 | | ALL |
| E-B | | | | | 0-0 | 33-21-14 | L00256 | | BLK | | | | SP00964 | | 9 | | ALL |
| E-C | | | | | 0-0 | 33-21-14 | L00256 | | WHT | | | | SP00966 | | 9 | | ALL |
| E-D | | | | | 0-0 | 33-21-14 | L00256 | | WHT | | | | SP00968 | | 9 | | ALL |
| F-A | | | | | 0-0 | 33-21-14 | L00257 | | BLK | | | | SP00954 | | 9 | | ALL |
| F-B | | | | | 0-0 | 33-21-14 | L00257 | | BLK | | | | SP00956 | | 9 | | ALL |
| F-C | | | | | 0-0 | 33-21-14 | L00257 | | WHT | | | | SP00958 | | 9 | | ALL |
| F-D | | | | | 0-0 | 33-21-14 | L00257 | | WHT | | | | SP00960 | | 9 | | ALL |
| G-A | | | | | 0-0 | 33-21-14 | L00258 | | BLK | | | | SP00978 | | 9 | | ALL |
| G-B | | | | | 0-0 | 33-21-14 | L00258 | | BLK | | | | SP00980 | | 9 | | ALL |
| G-C | | | | | 0-0 | 33-21-14 | L00258 | | WHT | | | | SP00982 | | 9 | | ALL |
| G-D | | | | | 0-0 | 33-21-14 | L00258 | | WHT | | | | SP00984 | | 9 | | ALL |
| H-A | | | | | 0-0 | 33-21-14 | L00259 | | BLK | | | | SP00970 | | 9 | | ALL |
| H-B | | | | | 0-0 | 33-21-14 | L00259 | | BLK | | | | SP00972 | | 9 | | ALL |
| H-C | | | | | 0-0 | 33-21-14 | L00259 | | WHT | | | | SP00974 | | 9 | | ALL |
| H-D | | | | | 0-0 | 33-21-14 | L00259 | | WHT | | | | SP00976 | | 9 | | ALL |
| J-A | | | | | 0-0 | 33-21-14 | L00260 | | BLK | | | | SP00994 | | 9 | | ALL |
| J-B | | | | | 0-0 | 33-21-14 | L00260 | | BLK | | | | SP00996 | | 9 | | ALL |
| J-C | | | | | 0-0 | 33-21-14 | L00260 | | WHT | | | | SP00998 | | 9 | | ALL |
| J-D | | | | | 0-0 | 33-21-14 | L00260 | | WHT | | | | SP01000 | | 9 | | ALL |
| K-A | | | | | 0-0 | 33-21-14 | L00261 | | BLK | | | | SP00986 | | 9 | | ALL |
| K-B | | | | | 0-0 | 33-21-14 | L00261 | | BLK | | | | SP00988 | | 9 | | ALL |
| K-C | | | | | 0-0 | 33-21-14 | L00261 | | WHT | | | | SP00990 | | 9 | | ALL |
| K-D | | | | | 0-0 | 33-21-14 | L00261 | | WHT | | | | SP00992 | | 9 | | ALL |
| L-A | | | | | 0-0 | 33-21-14 | L00274 | | BLK | | | | SP01010 | | 9 | | ALL |
| L-B | | | | | 0-0 | 33-21-14 | L00274 | | BLK | | | | SP01012 | | 9 | | ALL |
| L-C | | | | | 0-0 | 33-21-14 | L00274 | | WHT | | | | SP01014 | | 9 | | ALL |
| L-D | | | | | 0-0 | 33-21-14 | L00274 | | WHT | | | | SP01016 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 87

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0816 | 286T0816 | | | AFT CEILING AND SIDEWALL WASH LTS (continued) | | | | | | | | | | | |
| M-A | | | | | 0-0 | 33-21-14 | L00275 | | BLK | | SP01002 | | 9 | | ALL |
| M-B | | | | | 0-0 | 33-21-14 | L00275 | | BLK | | SP01004 | | 9 | | ALL |
| M-C | | | | | 0-0 | 33-21-14 | L00275 | | WHT | | SP01006 | | 9 | | ALL |
| M-D | | | | | 0-0 | 33-21-14 | L00275 | | WHT | | SP01008 | | 9 | | ALL |
| N-A | | | | | 0-0 | 33-21-14 | L00278 | | BLK | | SP01026 | | 9 | | ALL |
| N-B | | | | | 0-0 | 33-21-14 | L00278 | | BLK | | SP01028 | | 9 | | ALL |
| N-C | | | | | 0-0 | 33-21-14 | L00278 | | WHT | | SP01030 | | 9 | | ALL |
| N-D | | | | | 0-0 | 33-21-14 | L00278 | | WHT | | SP01032 | | 9 | | ALL |
| P-A | | | | | 0-0 | 33-21-14 | L00279 | | BLK | | SP01018 | | 9 | | ALL |
| P-B | | | | | 0-0 | 33-21-14 | L00279 | | BLK | | SP01020 | | 9 | | ALL |
| P-C | | | | | 0-0 | 33-21-14 | L00279 | | WHT | | SP01022 | | 9 | | ALL |
| P-D | | | | | 0-0 | 33-21-14 | L00279 | | WHT | | SP01024 | | 9 | | ALL |
| W0817 | 286T0817 | | | SATCOM SYSTEM CONTROL INTERFACES-E9 TO E2-3,E2-6 | | | | | | | | | | | |
| 001 | 24 | | | PK | 110-6 | 23-25-14 | D06159J | | 1 | | D06155J | | 23 | | 150, 153-199, 277-299 |
| 002 | 24 | | | PK | 110-6 | 23-25-14 | D06159J | | 2 | | D06155J | | 22 | | 150, 153-199, 277-299 |
| 003 | 24 | | | PV | 110-6 | 23-25-14 | D06159J | | 4 | | D06155J | | 21 | | 277-299 |
| 003Z | | | | AC | 0-0 | 23-25-14 | D06159J | | 3 | | D06155J | | 20 | | 277-299 |
| 004 | 24 | | | PV | 110-6 | 23-25-14 | D06159J | | 5 | | D06155J | | 19 | | 277-299 |
| 004Z | | | | AD | 0-0 | 23-25-14 | D06159J | | 6 | | D06155J | | 18 | | 277-299 |
| 201B | 24 | | | PW | 107-7 | 23-25-13 | D06157J | | 2 | | D06155J | | 5 | | 156-157, 166-199, 277-299 |
| 201R | 24 | | | PW | 0-0 | 23-25-13 | D06157J | | 1 | | D06155J | | 4 | | 156-157, 166-199, 277-299 |
| 201Z | | | | IA | 0-0 | 23-25-13 | D06157J | | 3 | | D06155J | | 24 | | 156-157, 166-199, 277-299 |
| 202B | 22 | | | PR | 107-7 | 23-25-13 | D06157J | | 6 | | D06155J | | 8 | | 150, 153-155, 162-165 |
| 202B | 24 | | | PW | 107-7 | 23-25-13 | D06157J | | 6 | | D06155J | | 8 | | 156-157, 166-199, 277-299 |
| 202R | 22 | | | PR | 0-0 | 23-25-13 | D06157J | | 5 | | D06155J | | 7 | | 150, 153-155, 162-165 |
| 202R | 24 | | | PW | 0-0 | 23-25-13 | D06157J | | 5 | | D06155J | | 7 | | 156-157, 166-199, 277-299 |
| 202Z | | | | IB | 0-0 | 23-25-13 | D06157J | | 4 | | D06155J | | 6 | | 150, 153-199, 277-299 |
| 203B | 22 | | | PR | 107-7 | 23-25-13 | D06157J | | 9 | | D06155J | | 3 | | 150, 153-155, 162-165 |
| 203B | 24 | | | PW | 107-7 | 23-25-13 | D06157J | | 9 | | D06155J | | 3 | | 156-157, 166-199, 277-299 |
| 203R | 22 | | | PR | 0-0 | 23-25-13 | D06157J | | 8 | | D06155J | | 2 | | 150, 153-155, 162-165 |
| 203R | 24 | | | PW | 0-0 | 23-25-13 | D06157J | | 8 | | D06155J | | 2 | | 156-157, 166-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 88
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|----|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0817 | 286T0817 | | | SATCOM SYSTEM CONTROL INTERFACES-E9 TO E2-3,E2-6 (continued) | | | | | | | | | | | | | |
| 203Z | | | | IC | 0-0 | 23-25-13 | D06157J | | 7 | | | | D06155J | | 1 | | 150, 153-199, 277-299 |
| 204B | 22 | | PR | ID | 107-7 | 23-25-13 | D06157J | | 12 | | | | D06155J | | 14 | | 150, 153-155, 162-165 |
| 204B | 24 | | PW | ID | 107-7 | 23-25-13 | D06157J | | 12 | | | | D06155J | | 14 | | 156-157, 166-199, 277-299 |
| 204R | 22 | | PR | ID | 0-0 | 23-25-13 | D06157J | | 11 | | | | D06155J | | 13 | | 150, 153-155, 162-165 |
| 204R | 24 | | PW | ID | 0-0 | 23-25-13 | D06157J | | 11 | | | | D06155J | | 13 | | 156-157, 166-199, 277-299 |
| 204Z | | | | ID | 0-0 | 23-25-13 | D06157J | | 10 | | | | D06155J | | 12 | | 150, 153-199, 277-299 |
| 205B | 24 | | PW | IE | 107-7 | 23-25-13 | D06157J | | 15 | | | | D06155J | | 17 | | 156-157, 166-199, 277-299 |
| 205R | 24 | | PW | IE | 0-0 | 23-25-13 | D06157J | | 14 | | | | D06155J | | 16 | | 156-157, 166-199, 277-299 |
| 205Z | | | | IE | 0-0 | 23-25-13 | D06157J | | 13 | | | | D06155J | | 15 | | 156-157, 166-199, 277-299 |
| 910 | 22 | | PA | | 110-6 | 23-25-14 | D06159J | | 8 | | | | D06155J | | 9 | | 150, 153-199 |
| 912B | 22 | | PR | HX | 110-6 | 23-25-14 | D06159J | | 6 | | | | D06155J | | 18 | | 150, 153-199 |
| 912R | 22 | | PR | HX | 0-0 | 23-25-14 | D06159J | | 5 | | | | D06155J | | 19 | | 150, 153-199 |
| 912Z | | | | HX | 0-0 | 23-25-14 | D06159J | | | | FA | | D06155J | DED | | | 150, 153-199 |
| 913B | 22 | | PR | HW | 110-6 | 23-25-14 | D06159J | | 3 | | | | D06155J | | 20 | | 150, 153-199 |
| 913R | 22 | | PR | HW | 0-0 | 23-25-14 | D06159J | | 4 | | | | D06155J | | 21 | | 150, 153-199 |
| 913Z | | | | HW | 0-0 | 23-25-14 | D06159J | | | | FA | | D06155J | DED | | | 150, 153-199 |
| FRA | | | | | 0-0 | 23-25-14 | D06159J | | | | FA | | D06159J | | 7 | | 150, 153-199 |
| W0818 | 286T0818 | | | AFT SIDEWALL WASH LTS,GALLEY LTS,DIRECT CLG LTS | | | | | | | | | | | | | |
| 001 | 20 | | PA | | 45-0 | 33-21-35 | D05120P | | 1 | | | | SM00010 | | 9 | | 150-154, 157-165, 167-199 |
| 001 | 20 | | PQ | AA | 45-0 | 33-21-35 | D05120P | | 1 | | | | SM00010 | | 9 | | 155-156, 166 |
| 001 | 20 | | PA | | 26-5 | 33-21-35 | D05120P | | 1 | | | | SM00010 | | 9 | | 275-299 |
| 001Z | | | | AA | 0-0 | 33-21-35 | D05120P | | DED | | | | SM00010 | DED | | | 155-156, 166 |
| 002 | 22 | | PA | | 2-0 | 33-21-35 | D05120P | | 2 | | | | SM00001 | | 9 | | 050-099 |
| 002 | 20 | | PA | | 2-0 | 33-21-35 | D05120P | | 2 | | | | SM00001 | | 9 | | 150-154, 157-165, 167-199, 275-299 |
| 002 | 20 | | PQ | AB | 2-0 | 33-21-35 | D05120P | | 2 | | | | SM00001 | | 9 | | 155-156, 166 |
| 002Z | | | | AB | 0-0 | 33-21-35 | D05120P | | DED | | | | SM00001 | DED | | | 155-156, 166 |
| 004 | 20 | | PA | | 5-0 | 33-21-35 | GD01028 | | A.. | E | | | D02094 | | 7 | | 050-099 |
| 004 | 20 | | PA | | 6-3 | 33-21-35 | GD04888 | | A.. | E | | | D02094 | | 7 | | 150-154, 157-165, 167-199, 275-299 |
| 004 | 20 | | PQ | AD | 6-3 | 33-21-35 | GD04888 | | A.. | E | | | D02094 | | 7 | | 155-156, 166 |
| 004Z | | | | AD | 0-0 | 33-21-35 | GD04888 | | DED | | | | D02094 | DED | | | 155-156, 166 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 89

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|--------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0818 | 286T0818 | | | AFT SIDEWALL WASH LTS,GALLEY LTS,DIRECT CLG LTS (continued) | | | | | | | | | | | |
| 005 | 20 | | PA | | 5-0 | 33-21-35 | GD01474 | S.. | E | | D02094 | | | | 050-099 |
| 005 | 20 | | PA | | 6-3 | 33-21-35 | GD04892 | S.. | E | | D02094 | | | | 150-199, 275-299 |
| 006 | 22 | | PA | | 18-0 | 33-21-35 | SM00001 | | | 9 | D02094 | | | | 050-099 |
| 006 | 20 | | PA | | 12-7 | 33-21-35 | SM00001 | | | 9 | D02094 | | | | 150-154, 157-165, 167-199 |
| 006 | 20 | | PQ | AF | 12-7 | 33-21-35 | SM00001 | | | 9 | D02094 | | | | 155-156, 166 |
| 006 | 20 | | PA | | 12-6 | 33-21-35 | SM00001 | | | 9 | D02094 | | | | 275-299 |
| 006Z | | | | AF | 0-0 | 33-21-35 | SM00001 | DED | | | D02094 | DED | | | 155-156, 166 |
| 007 | 22 | | PA | | 23-0 | 33-21-35 | SM00001 | | | 9 | D02096 | | | | 050-099 |
| 007 | 20 | | PA | | 21-0 | 33-21-35 | SM00001 | | | 9 | D02096 | | | | 150-154, 157-165, 167-199 |
| 007 | 20 | | PQ | AG | 21-0 | 33-21-35 | SM00001 | | | 9 | D02096 | | | | 155-156, 166 |
| 007 | 20 | | PA | | 20-3 | 33-21-35 | SM00001 | | | 9 | D02096 | | | | 275-299 |
| 007Z | | | | AG | 0-0 | 33-21-35 | SM00001 | DED | | | D02096 | DED | | | 155-156, 166 |
| 008 | 20 | | PA | | 3-0 | 33-21-35 | GD01476 | A.. | E | | D02096 | | | | 050-099 |
| 008 | 20 | | PA | | 4-0 | 33-21-35 | GD04928 | A.. | E | | D02096 | | | | 150-154, 162 |
| 008 | 20 | | PQ | AH | 11-0 | 33-21-35 | GD04928 | A.. | E | | D02096 | | | | 155-156, 166 |
| 008 | 20 | | PA | | 11-0 | 33-21-35 | GD04928 | A.. | E | | D02096 | | | | 157, 163-165, 167-199 |
| 008 | 20 | | PA | | 3-3 | 33-21-35 | GD04928 | A.. | E | | D02096 | | | | 275-299 |
| 008Z | | | | AH | 0-0 | 33-21-35 | GD04928 | DED | | | D02096 | DED | | | 155-156, 166 |
| 009 | 20 | | PA | | 3-0 | 33-21-35 | GD01478 | S.. | E | | D02096 | | | | 050-099 |
| 009 | 20 | | PA | | 4-0 | 33-21-35 | GD04932 | S.. | E | | D02096 | | | | 150-199 |
| 009 | 20 | | PA | | 3-3 | 33-21-35 | GD04932 | S.. | E | | D02096 | | | | 275-299 |
| 010 | 22 | | PA | | 67-0 | 33-21-35 | D02094 | | | 2 | D03152 | | | | 050-099 |
| 010 | 22 | | PA | | 12-1 | 33-21-35 | D02094 | | | 2 | D03130 | | | | 150-199 |
| 010 | 22 | | PA | | 12-2 | 33-21-35 | D02094 | | | 2 | D03130 | | | | 275-299 |
| 011 | 22 | | PA | | 67-0 | 33-21-35 | D02094 | | | 3 | D03152 | | | | 050-099 |
| 011 | 22 | | PA | | 12-1 | 33-21-35 | D02094 | | | 3 | D03130 | | | | 150-199 |
| 011 | 22 | | PA | | 12-2 | 33-21-35 | D02094 | | | 3 | D03130 | | | | 275-299 |
| 012 | 22 | | PA | | 60-0 | 33-21-35 | SM00002 | | | 9 | D03152 | | | | 050-099 |
| 012 | 22 | | PA | | 8-0 | 33-21-35 | SM00002 | | | 9 | D03130 | | | | 150-199 |
| 012 | 22 | | PA | | 7-5 | 33-21-35 | SM00002 | | | 9 | D03130 | | | | 275-299 |
| 013 | 22 | | PA | | 60-0 | 33-21-35 | SM00003 | | | 9 | D03152 | | | | 050-099 |
| 013 | 22 | | PA | | 8-0 | 33-21-35 | SM00003 | | | 9 | D03130 | | | | 150-199 |
| 013 | 22 | | PA | | 7-5 | 33-21-35 | SM00003 | | | 9 | D03130 | | | | 275-299 |
| 014 | 22 | | PA | | 8-0 | 33-21-35 | SM00002 | | | 9 | D03132 | | | | 050-099 |
| 014 | 22 | | PA | | 10-0 | 33-21-35 | SM00004 | | | 9 | D03132 | | | | 150-199 |
| 014 | 22 | | PA | | 9-6 | 33-21-35 | SM00004 | | | 9 | D03132 | | | | 275-299 |
| 015 | 22 | | PA | | 8-0 | 33-21-35 | SM00003 | | | 9 | D03132 | | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 90

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|---|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0818 | 286T0818 | | | AFT SIDEWALL WASH LTS,GALLEY LTS,DIRECT CLG LTS (continued) | | | | | | | | | | | | | |
| 015 | 22 | | PA | 10-0 | 33-21-35 | SM00005 | | | 9 | | | | D03132 | 4 | | | 150-199 |
| 015 | 22 | | PA | 9-6 | 33-21-35 | SM00005 | | | 9 | | | | D03132 | 4 | | | 275-299 |
| 016 | 22 | | PA | 14-0 | 33-21-35 | D02094 | | | 9 | | | | D03132 | 1 | | | 050-099 |
| 016 | 22 | | PA | 8-0 | 33-21-35 | D02096 | | | 9 | | | | D03132 | 1 | | | 150-199 |
| 016 | 22 | | PA | 7-2 | 33-21-35 | D02096 | | | 9 | | | | D03132 | 1 | | | 275-299 |
| 017 | 22 | | PA | 14-0 | 33-21-35 | D02094 | | | 10 | | | | D03132 | 2 | | | 050-099 |
| 017 | 22 | | PA | 8-0 | 33-21-35 | D02096 | | | 10 | | | | D03132 | 2 | | | 150-199 |
| 017 | 22 | | PA | 7-2 | 33-21-35 | D02096 | | | 10 | | | | D03132 | 2 | | | 275-299 |
| 018 | 22 | | PA | 8-0 | 33-21-35 | D02094 | | | 11 | | | | SM00002 | | 9 | | 050-099 |
| 018 | 22 | | PA | 6-9 | 33-21-35 | D02094 | | | 11 | | | | SM00002 | | 9 | | 150-199, 275-299 |
| 019 | 22 | | PA | 8-0 | 33-21-35 | D02094 | | | 12 | | | | SM00003 | | 9 | | 050-099 |
| 019 | 22 | | PA | 6-9 | 33-21-35 | D02094 | | | 12 | | | | SM00003 | | 9 | | 150-199, 275-299 |
| 020 | 22 | | PA | 6-0 | 33-21-35 | D02096 | | | 2 | | | | D03134 | 1 | | | 050-099 |
| 020 | 22 | | PA | 13-0 | 33-21-35 | D02096 | | | 2 | | | | D03134 | 1 | | | 150-199, 275-299 |
| 021 | 22 | | PA | 6-0 | 33-21-35 | D02096 | | | 3 | | | | D03134 | 2 | | | 050-099 |
| 021 | 22 | | PA | 13-0 | 33-21-35 | D02096 | | | 3 | | | | D03134 | 2 | | | 150-199, 275-299 |
| 022 | 22 | | PA | 7-0 | 33-21-35 | SM00004 | | | 9 | | | | D03134 | 3 | | | 050-099 |
| 022 | 22 | | PA | 8-0 | 33-21-35 | SM00004 | | | 9 | | | | D03134 | 3 | | | 150-199 |
| 022 | 22 | | PA | 7-1 | 33-21-35 | SM00004 | | | 9 | | | | D03134 | 3 | | | 275-299 |
| 023 | 22 | | PA | 7-0 | 33-21-35 | SM00005 | | | 9 | | | | D03134 | 4 | | | 050-099 |
| 023 | 22 | | PA | 8-0 | 33-21-35 | SM00005 | | | 9 | | | | D03134 | 4 | | | 150-199 |
| 023 | 22 | | PA | 7-1 | 33-21-35 | SM00005 | | | 9 | | | | D03134 | 4 | | | 275-299 |
| 024 | 22 | | PA | 9-0 | 33-21-35 | SM00004 | | | 9 | | | | D03136 | 3 | | | 050-099 |
| 024 | 22 | | PA | 10-0 | 33-21-35 | SM00013 | | | 9 | | | | D03136 | 3 | | | 150-199 |
| 024 | 22 | | PA | 8-11 | 33-21-35 | SM00013 | | | 9 | | | | D03136 | 3 | | | 275-299 |
| 025 | 22 | | PA | 9-0 | 33-21-35 | SM00005 | | | 9 | | | | D03136 | 4 | | | 050-099 |
| 025 | 22 | | PA | 10-0 | 33-21-35 | SM00014 | | | 9 | | | | D03136 | 4 | | | 150-199 |
| 025 | 22 | | PA | 8-11 | 33-21-35 | SM00014 | | | 9 | | | | D03136 | 4 | | | 275-299 |
| 026 | 22 | | PA | 12-0 | 33-21-35 | D02096 | | | 9 | | | | D03136 | 1 | | | 050-099 |
| 026 | 22 | | PA | 14-0 | 33-21-35 | D11252 | | | 9 | | | | D03136 | 1 | | | 150-199 |
| 026 | 22 | | PA | 13-0 | 33-21-35 | D11252 | | | 9 | | | | D03136 | 1 | | | 275-299 |
| 027 | 22 | | PA | 12-0 | 33-21-35 | D02096 | | | 10 | | | | D03136 | 2 | | | 050-099 |
| 027 | 22 | | PA | 14-0 | 33-21-35 | D11252 | | | 10 | | | | D03136 | 2 | | | 150-199 |
| 027 | 22 | | PA | 13-0 | 33-21-35 | D11252 | | | 10 | | | | D03136 | 2 | | | 275-299 |
| 028 | 22 | | PA | 5-0 | 33-21-35 | D02096 | | | 11 | | | | SM00004 | | 9 | | 050-099 |
| 028 | 22 | | PA | 8-0 | 33-21-35 | D02096 | | | 11 | | | | SM00004 | | 9 | | 150-199 |
| 028 | 22 | | PA | 7-0 | 33-21-35 | D02096 | | | 11 | | | | SM00004 | | 9 | | 275-299 |
| 029 | 22 | | PA | 5-0 | 33-21-35 | D02096 | | | 12 | | | | SM00005 | | 9 | | 050-099 |
| 029 | 22 | | PA | 8-0 | 33-21-35 | D02096 | | | 12 | | | | SM00005 | | 9 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 91

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0818 | 286T0818 | | | AFT SIDEWALL WASH LTS,GALLEY LTS,DIRECT CLG LTS (continued) | | | | | | | | | | | |
| 029 | 22 | | PA | | 7-0 | 33-21-35 | D02096 | | 12 | | SM00005 | | 9 | | 275-299 |
| 036 | 22 | | PA | | 31-0 | 33-21-35 | SM00001 | | 9 | | D02098 | | 5 | | 050-099 |
| 036 | 20 | | PA | | 43-0 | 33-21-35 | SM00001 | | 9 | | D02098 | | 5 | | 150-154, 157-165, 167-199 |
| 036 | 20 | | PQ | BK | 43-0 | 33-21-35 | SM00001 | | 9 | | D02098 | | 5 | | 155-156, 166 |
| 036 | 20 | | PA | | 42-2 | 33-21-35 | SM00001 | | 9 | | D02098 | | 5 | | 275-299 |
| 036Z | | | | BK | 0-0 | 33-21-35 | SM00001 | | DED | | D02098 | | DED | | 155-156, 166 |
| 037 | 20 | | PA | | 3-0 | 33-21-35 | GD01486 | | S.. | E | D02098 | | 8 | | 050-099, 275-299 |
| 037 | 20 | | PA | | 4-0 | 33-21-35 | GD01486 | | S.. | E | D02098 | | 8 | | 150-199 |
| 038 | 20 | | PA | | 3-0 | 33-21-35 | GD01032 | | A.. | E | D02098 | | 7 | | 050-099, 275-299 |
| 038 | 20 | | PA | | 4-0 | 33-21-35 | GD01032 | | A.. | E | D02098 | | 7 | | 150-154, 157-165, 167-199 |
| 038 | 20 | | PQ | BM | 4-0 | 33-21-35 | GD01032 | | A.. | E | D02098 | | 7 | | 155-156, 166 |
| 038Z | | | | BM | 0-0 | 33-21-35 | GD01032 | | DED | | D02098 | | DED | | 155-156, 166 |
| 039 | 22 | | PA | | 7-0 | 33-21-35 | D02098 | | 2 | | D03140 | | 1 | | 050-099, 150-199 |
| 039 | 22 | | PA | | 6-8 | 33-21-35 | D02098 | | 2 | | D03140 | | 1 | | 275-299 |
| 040 | 22 | | PA | | 7-0 | 33-21-35 | D02098 | | 3 | | D03140 | | 2 | | 050-099, 150-199 |
| 040 | 22 | | PA | | 6-8 | 33-21-35 | D02098 | | 3 | | D03140 | | 2 | | 275-299 |
| 041 | 22 | | PA | | 7-0 | 33-21-35 | SM00006 | | | 9 | D03140 | | 3 | | 050-099 |
| 041 | 22 | | PA | | 8-0 | 33-21-35 | SM00006 | | | 9 | D03140 | | 3 | | 150-199 |
| 041 | 22 | | PA | | 7-8 | 33-21-35 | SM00006 | | | 9 | D03140 | | 3 | | 275-299 |
| 042 | 22 | | PA | | 7-0 | 33-21-35 | SM00007 | | | 9 | D03140 | | 4 | | 050-099 |
| 042 | 22 | | PA | | 8-0 | 33-21-35 | SM00007 | | | 9 | D03140 | | 4 | | 150-199 |
| 042 | 22 | | PA | | 7-8 | 33-21-35 | SM00007 | | | 9 | D03140 | | 4 | | 275-299 |
| 043 | 22 | | PA | | 10-0 | 33-21-35 | SM00006 | | | 9 | D03142 | | 3 | | 050-099 |
| 043 | 22 | | PA | | 9-0 | 33-21-35 | SM00006 | | | 9 | D03142 | | 3 | | 150-199 |
| 043 | 22 | | PA | | 8-9 | 33-21-35 | SM00006 | | | 9 | D03142 | | 3 | | 275-299 |
| 044 | 22 | | PA | | 10-0 | 33-21-35 | SM00007 | | | 9 | D03142 | | 4 | | 050-099 |
| 044 | 22 | | PA | | 9-0 | 33-21-35 | SM00007 | | | 9 | D03142 | | 4 | | 150-199 |
| 044 | 22 | | PA | | 8-9 | 33-21-35 | SM00007 | | | 9 | D03142 | | 4 | | 275-299 |
| 045 | 22 | | PA | | 13-0 | 33-21-35 | D02098 | | | 9 | D03142 | | 1 | | 050-099 |
| 045 | 22 | | PA | | 14-0 | 33-21-35 | D02098 | | | 9 | D03142 | | 1 | | 150-199 |
| 045 | 22 | | PA | | 12-7 | 33-21-35 | D02098 | | | 9 | D03142 | | 1 | | 275-299 |
| 046 | 22 | | PA | | 13-0 | 33-21-35 | D02098 | | | 10 | D03142 | | 2 | | 050-099 |
| 046 | 22 | | PA | | 14-0 | 33-21-35 | D02098 | | | 10 | D03142 | | 2 | | 150-199 |
| 046 | 22 | | PA | | 12-7 | 33-21-35 | D02098 | | | 10 | D03142 | | 2 | | 275-299 |
| 047 | 22 | | PA | | 5-0 | 33-21-35 | D02098 | | | 11 | SM00006 | | 9 | | 050-099, 150-199 |
| 047 | 22 | | PA | | 4-4 | 33-21-35 | D02098 | | | 11 | SM00006 | | 9 | | 275-299 |
| 048 | 22 | | PA | | 5-0 | 33-21-35 | D02098 | | | 12 | SM00007 | | 9 | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 92

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|---|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0818 | 286T0818 | | | AFT SIDEWALL WASH LTS,GALLEY LTS,DIRECT CLG LTS (continued) | | | | | | | | | | | | | |
| 048 | 22 | | PA | 4-4 | 33-21-35 | D02098 | | 12 | | | | | SM00007 | | 9 | | 275-299 |
| 049 | 22 | | PA | 38-0 | 33-21-35 | SM00001 | | | 9 | | | | D02100 | | 5 | | 050-099 |
| 049 | 20 | | PA | 53-0 | 33-21-35 | SM00001 | | | 9 | | | | D02100 | | 5 | | 150-154, 162-165 |
| 049 | 20 | | PQ | 50-0 | 33-21-35 | SM00001 | BX | | 9 | | | | D02100 | | 5 | | 155-156, 166 |
| 049 | 20 | | PA | 50-0 | 33-21-35 | SM00001 | | | 9 | | | | D02100 | | 5 | | 157, 167-199 |
| 049 | 20 | | PA | 49-6 | 33-21-35 | SM00001 | | | 9 | | | | D02100 | | 5 | | 275-299 |
| 049Z | | | | 0-0 | 33-21-35 | SM00001 | BX | DED | | | | | D02100 | DED | | | 155-156, 166 |
| 050 | 20 | | PA | 2-0 | 33-21-35 | GD01530 | | S.. | E | | | | D02100 | | 8 | | 050-099 |
| 050 | 20 | | PA | 10-0 | 33-21-35 | GD01530 | | S.. | E | | | | D02100 | | 8 | | 150-199 |
| 050 | 20 | | PA | 3-4 | 33-21-35 | GD01530 | | S.. | E | | | | D02100 | | 8 | | 275-299 |
| 051 | 20 | | PA | 3-0 | 33-21-35 | GD01528 | | A.. | E | | | | D02100 | | 7 | | 050-099 |
| 051 | 20 | | PA | 10-0 | 33-21-35 | GD01528 | | A.. | E | | | | D02100 | | 7 | | 150-154, 162-165 |
| 051 | 20 | | PQ | 4-0 | 33-21-35 | GD01528 | CA | A.. | E | | | | D02100 | | 7 | | 155-156, 166 |
| 051 | 20 | | PA | 4-0 | 33-21-35 | GD01528 | | A.. | E | | | | D02100 | | 7 | | 157, 167-199 |
| 051 | 20 | | PA | 3-4 | 33-21-35 | GD01528 | | A.. | E | | | | D02100 | | 7 | | 275-299 |
| 051Z | | | | 0-0 | 33-21-35 | GD01528 | CA | DED | | | | | D02100 | DED | | | 155-156, 166 |
| 052 | 22 | | PA | 9-0 | 33-21-35 | D02100 | | | 2 | | | | D03144 | | 1 | | 050-099 |
| 052 | 22 | | PA | 17-0 | 33-21-35 | D02100 | | | 2 | | | | D03144 | | 1 | | 150-199 |
| 052 | 22 | | PA | 7-5 | 33-21-35 | D02100 | | | 2 | | | | D03144 | | 1 | | 275-299 |
| 053 | 22 | | PA | 9-0 | 33-21-35 | D02100 | | | 3 | | | | D03144 | | 2 | | 050-099 |
| 053 | 22 | | PA | 17-0 | 33-21-35 | D02100 | | | 3 | | | | D03144 | | 2 | | 150-199 |
| 053 | 22 | | PA | 7-5 | 33-21-35 | D02100 | | | 3 | | | | D03144 | | 2 | | 275-299 |
| 054 | 22 | | PA | 8-0 | 33-21-35 | SM00008 | | | 9 | | | | D03144 | | 3 | | 050-099, 150-199 |
| 054 | 22 | | PA | 7-0 | 33-21-35 | SM00008 | | | 9 | | | | D03144 | | 3 | | 275-299 |
| 055 | 22 | | PA | 8-0 | 33-21-35 | SM00009 | | | 9 | | | | D03144 | | 4 | | 050-099, 150-199 |
| 055 | 22 | | PA | 7-0 | 33-21-35 | SM00009 | | | 9 | | | | D03144 | | 4 | | 275-299 |
| 056 | 22 | | PA | 9-0 | 33-21-35 | SM00008 | | | 9 | | | | D03146 | | 3 | | 050-099, 150-199 |
| 056 | 22 | | PA | 8-10 | 33-21-35 | SM00008 | | | 9 | | | | D03146 | | 3 | | 275-299 |
| 057 | 22 | | PA | 9-0 | 33-21-35 | SM00009 | | | 9 | | | | D03146 | | 4 | | 050-099, 150-199 |
| 057 | 22 | | PA | 8-10 | 33-21-35 | SM00009 | | | 9 | | | | D03146 | | 4 | | 275-299 |
| 058 | 22 | | PA | 12-0 | 33-21-35 | D02100 | | | 9 | | | | D03146 | | 1 | | 050-099 |
| 058 | 22 | | PA | 13-0 | 33-21-35 | D02100 | | | 9 | | | | D03146 | | 1 | | 150-199 |
| 058 | 22 | | PA | 12-5 | 33-21-35 | D02100 | | | 9 | | | | D03146 | | 1 | | 275-299 |
| 059 | 22 | | PA | 12-0 | 33-21-35 | D02100 | | | 10 | | | | D03146 | | 2 | | 050-099 |
| 059 | 22 | | PA | 13-0 | 33-21-35 | D02100 | | | 10 | | | | D03146 | | 2 | | 150-199 |
| 059 | 22 | | PA | 12-5 | 33-21-35 | D02100 | | | 10 | | | | D03146 | | 2 | | 275-299 |
| 060 | 22 | | PA | 5-0 | 33-21-35 | D02100 | | | 11 | | | | SM00008 | | 9 | | 050-099 |
| 060 | 22 | | PA | 10-0 | 33-21-35 | D02100 | | | 11 | | | | SM00008 | | 9 | | 150-199 |
| 060 | 22 | | PA | 4-1 | 33-21-35 | D02100 | | | 11 | | | | SM00008 | | 9 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 93

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|------|------|---------|-------------|--|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0818 | 286T0818 | | | AFT SIDEWALL WASH LTS,GALLEY LTS,DIRECT CLG LTS (continued) | | | | | | | | | | | | | | |
| 061 | 22 | PA | | | 5-0 | 33-21-35 | D02100 | 12 | | | | | | | SM00009 | 9 | | 050-099 |
| 061 | 22 | PA | | | 10-0 | 33-21-35 | D02100 | 12 | | | | | | | SM00009 | 9 | | 150-199 |
| 061 | 22 | PA | | | 4-1 | 33-21-35 | D02100 | 12 | | | | | | | SM00009 | 9 | | 275-299 |
| 062 | 20 | PA | | | 4-0 | 33-21-35 | GD02174 | | S.. | E | | | | | D03152 | 5 | | 050-099 |
| 062 | 20 | PA | | | 4-0 | 33-21-35 | GD02068 | | S.. | E | | | | | D03130 | 5 | | 150-199 |
| 062 | 20 | PA | | | 2-11 | 33-21-35 | GD02068 | | S.. | E | | | | | D03130 | 5 | | 275-299 |
| 063 | 20 | PA | | | 3-0 | 33-21-35 | GD02070 | | S.. | E | | | | | D03132 | 5 | | 050-099 |
| 063 | 20 | PA | | | 4-0 | 33-21-35 | GD02070 | | S.. | E | | | | | D03132 | 5 | | 150-199 |
| 063 | 20 | PA | | | 2-8 | 33-21-35 | GD02070 | | S.. | E | | | | | D03132 | 5 | | 275-299 |
| 064 | 20 | PA | | | 3-0 | 33-21-35 | GD02072 | | S.. | E | | | | | D03134 | 5 | | 050-099 |
| 064 | 20 | PA | | | 4-0 | 33-21-35 | GD02072 | | S.. | E | | | | | D03134 | 5 | | 150-199 |
| 064 | 20 | PA | | | 2-8 | 33-21-35 | GD02072 | | S.. | E | | | | | D03134 | 5 | | 275-299 |
| 065 | 20 | PA | | | 3-0 | 33-21-35 | GD02074 | | S.. | E | | | | | D03136 | 5 | | 050-099 |
| 065 | 20 | PA | | | 4-0 | 33-21-35 | GD02074 | | S.. | E | | | | | D03136 | 5 | | 150-199 |
| 065 | 20 | PA | | | 2-7 | 33-21-35 | GD02074 | | S.. | E | | | | | D03136 | 5 | | 275-299 |
| 067 | 20 | PA | | | 3-0 | 33-21-35 | GD02192 | | S.. | E | | | | | D03140 | 5 | | 050-099, 150-199 |
| 067 | 20 | PA | | | 2-5 | 33-21-35 | GD02192 | | S.. | E | | | | | D03140 | 5 | | 275-299 |
| 068 | 20 | PA | | | 4-0 | 33-21-35 | GD02194 | | S.. | E | | | | | D03142 | 5 | | 050-099, 150-199 |
| 068 | 20 | PA | | | 2-8 | 33-21-35 | GD02194 | | S.. | E | | | | | D03142 | 5 | | 275-299 |
| 069 | 20 | PA | | | 3-0 | 33-21-35 | GD02196 | | S.. | E | | | | | D03144 | 5 | | 050-099 |
| 069 | 20 | PA | | | 4-0 | 33-21-35 | GD02196 | | S.. | E | | | | | D03144 | 5 | | 150-199 |
| 069 | 20 | PA | | | 2-10 | 33-21-35 | GD02196 | | S.. | E | | | | | D03144 | 5 | | 275-299 |
| 070 | 20 | PA | | | 3-0 | 33-21-35 | GD02198 | | S.. | E | | | | | D03146 | 5 | | 050-099 |
| 070 | 20 | PA | | | 4-0 | 33-21-35 | GD02198 | | S.. | E | | | | | D03146 | 5 | | 150-199 |
| 070 | 20 | PA | | | 2-8 | 33-21-35 | GD02198 | | S.. | E | | | | | D03146 | 5 | | 275-299 |
| 071 | 20 | PA | | | 11-0 | 33-21-35 | D11252 | 5 | | | | | | | SM00010 | 9 | | 150-154, 157-165, 167-199 |
| 071 | 20 | PQ | CU | | 11-0 | 33-21-35 | D11252 | 5 | | | | | | | SM00010 | 9 | | 155-156, 166 |
| 071 | 20 | PA | | | 10-4 | 33-21-35 | D11252 | 5 | | | | | | | SM00010 | 9 | | 275-299 |
| 071Z | | | CU | | 0-0 | 33-21-35 | D11252 | | DED | | | | | | SM00010 | DED | | 155-156, 166 |
| 072 | 20 | PA | | | 5-0 | 33-21-35 | D11250 | 5 | | | | | | | SM00010 | 9 | | 150-154, 157-165, 167-199 |
| 072 | 20 | PQ | CV | | 5-0 | 33-21-35 | D11250 | 5 | | | | | | | SM00010 | 9 | | 155-156, 166 |
| 072 | 20 | PA | | | 4-2 | 33-21-35 | D11250 | 5 | | | | | | | SM00010 | 9 | | 275-299 |
| 072Z | | | CV | | 0-0 | 33-21-35 | D11250 | | DED | | | | | | SM00010 | DED | | 155-156, 166 |
| 073 | 20 | PA | | | 5-0 | 33-21-35 | D11250 | 8 | | | | | | | GD04948 | S.. E | | 150-199 |
| 073 | 20 | PA | | | 3-8 | 33-21-35 | D11250 | 8 | | | | | | | GD04948 | S.. E | | 275-299 |
| 074 | 20 | PA | | | 5-0 | 33-21-35 | D11250 | 7 | | | | | | | GD04944 | A.. E | | 150-154, 157-165, 167-199 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 94
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|---|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0818 | 286T0818 | | | AFT SIDEWALL WASH LTS,GALLEY LTS,DIRECT CLG LTS (continued) | | | | | | | | | | | | |
| 074 | 20 | PQ | CX | 5-0 | 33-21-35 | D11250 | | 7 | | | | | GD04944 | A.. | E | 155-156, 166 |
| 074 | 20 | PA | | 3-8 | 33-21-35 | D11250 | | 7 | | | | | GD04944 | A.. | E | 275-299 |
| 074Z | | | CX | 0-0 | 33-21-35 | D11250 | | | DED | | | | GD04944 | DED | | 155-156, 166 |
| 093 | 22 | PA | | 9-8 | 33-21-35 | SM00002 | | | 9 | | | | D03126 | 3 | | 150-199 |
| 093 | 22 | PA | | 9-7 | 33-21-35 | SM00002 | | | 9 | | | | D03126 | 3 | | 275-299 |
| 094 | 22 | PA | | 9-8 | 33-21-35 | SM00003 | | | 9 | | | | D03126 | 4 | | 150-199 |
| 094 | 22 | PA | | 9-7 | 33-21-35 | SM00003 | | | 9 | | | | D03126 | 4 | | 275-299 |
| 095 | 22 | PA | | 6-6 | 33-21-35 | D02094 | | 9 | | | | | D03126 | 1 | | 150-199 |
| 095 | 22 | PA | | 6-7 | 33-21-35 | D02094 | | 9 | | | | | D03126 | 1 | | 275-299 |
| 096 | 22 | PA | | 6-6 | 33-21-35 | D02094 | | 10 | | | | | D03126 | 2 | | 150-199 |
| 096 | 22 | PA | | 6-7 | 33-21-35 | D02094 | | 10 | | | | | D03126 | 2 | | 275-299 |
| 097 | 20 | PA | | 3-9 | 33-21-35 | GD02064 | | S.. | E | | | | D03126 | 5 | | 150-199, 275-299 |
| 105 | 22 | PA | | 5-0 | 33-21-35 | D11250 | | 11 | | | | | SM00011 | | 9 | 150-199 |
| 105 | 22 | PA | | 4-2 | 33-21-35 | D11250 | | 11 | | | | | SM00011 | | 9 | 275-299 |
| 106 | 22 | PA | | 5-0 | 33-21-35 | D11250 | | 12 | | | | | SM00012 | | 9 | 150-199 |
| 106 | 22 | PA | | 4-2 | 33-21-35 | D11250 | | 12 | | | | | SM00012 | | 9 | 275-299 |
| 107 | 20 | PA | | 5-0 | 33-21-35 | D11252 | | 8 | | | | | GD04898 | S.. | E | 150-199 |
| 107 | 20 | PA | | 3-7 | 33-21-35 | D11252 | | 8 | | | | | GD04898 | S.. | E | 275-299 |
| 108 | 20 | PA | | 5-0 | 33-21-35 | D11252 | | 7 | | | | | GD04894 | A.. | E | 150-154, 157-165, 167-199 |
| 108 | 20 | PQ | EH | 5-0 | 33-21-35 | D11252 | | 7 | | | | | GD04894 | A.. | E | 155-156, 166 |
| 108 | 20 | PA | | 3-7 | 33-21-35 | D11252 | | 7 | | | | | GD04894 | A.. | E | 275-299 |
| 108Z | | | EH | 0-0 | 33-21-35 | D11252 | | | DED | | | | GD04894 | DED | | 155-156, 166 |
| 115 | 22 | PA | | 6-0 | 33-21-35 | D11252 | | 11 | | | | | SM00013 | | 9 | 150-199 |
| 115 | 22 | PA | | 4-7 | 33-21-35 | D11252 | | 11 | | | | | SM00013 | | 9 | 275-299 |
| 116 | 22 | PA | | 6-0 | 33-21-35 | D11252 | | 12 | | | | | SM00014 | | 9 | 150-199 |
| 116 | 22 | PA | | 4-7 | 33-21-35 | D11252 | | 12 | | | | | SM00014 | | 9 | 275-299 |
| 130 | 22 | PA | | 7-0 | 33-21-35 | D11250 | | 2 | | | | | D11244 | 1 | | 150-199 |
| 130 | 22 | PA | | 6-10 | 33-21-35 | D11250 | | 2 | | | | | D11244 | 1 | | 275-299 |
| 131 | 22 | PA | | 7-0 | 33-21-35 | D11250 | | 3 | | | | | D11244 | 2 | | 150-199 |
| 131 | 22 | PA | | 6-10 | 33-21-35 | D11250 | | 3 | | | | | D11244 | 2 | | 275-299 |
| 132 | 22 | PA | | 8-0 | 33-21-35 | SM00011 | | | 9 | | | | D11244 | 3 | | 150-199 |
| 132 | 22 | PA | | 7-5 | 33-21-35 | SM00011 | | | 9 | | | | D11244 | 3 | | 275-299 |
| 133 | 22 | PA | | 8-0 | 33-21-35 | SM00012 | | | 9 | | | | D11244 | 4 | | 150-199 |
| 133 | 22 | PA | | 7-5 | 33-21-35 | SM00012 | | | 9 | | | | D11244 | 4 | | 275-299 |
| 134 | 20 | PA | | 4-0 | 33-21-35 | D11244 | | 5 | | | | | GD04982 | S.. | E | 150-199 |
| 134 | 20 | PA | | 3-5 | 33-21-35 | D11244 | | 5 | | | | | GD04982 | S.. | E | 275-299 |
| 147 | 22 | PA | | 58-1 | 33-22-42 | D06052J | | 23 | | | | | D05120P | 4 | | 275-299 |
| 148 | 20 | PA | | 8-11 | 33-22-42 | D06052J | | 20 | | | | | GD01120 | A.. | 2 | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 95

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|----------|-------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0818 | 286T0818 | | | AFT SIDEWALL WASH LTS,GALLEY LTS,DIRECT CLG LTS (continued) | | | | | | | | | | | | |
| 150 | 22 | PA | | 22-11 | 33-22-42 | | D06052J | | 3 | | | D06042J | | 2 | | 275-299 |
| 151 | 22 | PA | | 22-11 | 33-22-42 | | D06052J | | 2 | | | D06042J | | 1 | | 275-299 |
| 154 | 22 | PA | | 22-11 | 33-22-42 | | D06042J | | 9 | | | D06052J | | 14 | | 275-299 |
| 155 | 22 | PA | | 22-11 | 33-22-42 | | D06042J | | 10 | | | D06052J | | 15 | | 275-299 |
| 156 | 22 | PA | | 77-1 | 33-22-42 | | D06042J | | 21 | | | D05120P | | 5 | | 275-299 |
| 157 | 20 | PA | | 7-10 | 33-22-42 | | D06042J | | 22 | | | GD01126 | A.. | 2 | | 275-299 |
| 161 | 22 | PA | | 22-11 | 33-22-42 | | D06042J | | 7 | | | D06052J | | 19 | | 275-299 |
| 162 | 22 | PA | | 22-11 | 33-22-42 | | D06042J | | 6 | | | D06052J | | 18 | | 275-299 |
| 163 | 22 | PA | | 22-11 | 33-22-42 | | D06042J | | 16 | | | D06052J | | 12 | | 275-299 |
| 164 | 22 | PA | | 22-11 | 33-22-42 | | D06042J | | 17 | | | D06052J | | 11 | | 275-299 |
| 165 | 22 | PA | | 77-1 | 33-22-42 | | D06042J | | 19 | | | D05120P | | 8 | | 275-299 |
| 166 | 20 | PA | | 7-10 | 33-22-42 | | D06042J | | 20 | | | GD01126 | A.. | 2 | | 275-299 |
| 172 | 22 | PA | | 22-11 | 33-22-42 | | D06052J | | 6 | | | D06042J | | 5 | | 275-299 |
| 173 | 22 | PA | | 22-11 | 33-22-42 | | D06052J | | 7 | | | D06042J | | 4 | | 275-299 |
| 174 | 22 | PA | | 22-11 | 33-22-42 | | D06052J | | 8 | | | D06042J | | 12 | | 275-299 |
| 175 | 22 | PA | | 22-11 | 33-22-42 | | D06052J | | 9 | | | D06042J | | 11 | | 275-299 |
| 176 | 22 | PA | | 22-11 | 33-22-42 | | D06052J | | 17 | | | D06042J | | 14 | | 275-299 |
| 177 | 22 | PA | | 22-11 | 33-22-42 | | D06052J | | 16 | | | D06042J | | 15 | | 275-299 |
| 179 | 20 | PA | | 8-11 | 33-22-42 | | D06052J | | 10 | | | GD01120 | S.. | 2 | | 275-299 |
| 183 | 20 | PA | | 7-10 | 33-22-42 | | D06042J | | 13 | | | GD01126 | S.. | 2 | | 275-299 |
| 186 | 22 | PA | | 53-0 | 33-22-42 | | D06038J | | 4 | | | D05120P | | 6 | | 050-099 |
| 186 | 20 | PA | | 65-0 | 33-22-42 | | L01061 | =P | | C | | D05120P | | 7 | | 150-199 |
| 186 | 22 | PA | | 30-11 | 33-27-11 | | SM00015 | | | S | | D06038J | | 4 | | 275-299 |
| 187 | 20 | PA | | 10-0 | 33-22-42 | | D06038J | | 1 | | | GD01120 | A.. | 2 | | 050-099 |
| 187 | 20 | PA | | 9-6 | 33-27-11 | | D06038J | | 1 | | | GD01120 | A.. | 2 | | 275-299 |
| 195 | 22 | PA | | 53-0 | 33-22-42 | | D06038J | | 5 | | | D05120P | | 7 | | 050-099 |
| 195 | 20 | PA | | 7-0 | SPARE | | L00220 | =P | | C | * | L00219 | =P | C | | 150-199 |
| 195 | 22 | PA | | 64-4 | 33-27-11 | | D05120P | | 7 | | | D06038J | | 5 | | 275-299 |
| 196 | 20 | PA | | 10-0 | 33-22-42 | | D06038J | | 9 | | | GD01120 | A.. | 2 | | 050-099 |
| 196 | 20 | PA | | 9-6 | 33-27-11 | | D06038J | | 9 | | | GD01120 | A.. | 2 | | 275-299 |
| 500 | 22 | PA | | 40-7 | 33-27-11 | | SM00015 | | | S | | D02884 | | 5 | | 275-299 |
| 503 | 20 | PA | | 10-0 | 33-22-42 | | D06038J | | 6 | | | GD01120 | S.. | 2 | | 050-099 |
| 503 | 20 | PA | | 9-6 | 33-27-11 | | D06038J | | 6 | | | GD01120 | S.. | 2 | | 275-299 |
| 505 | 20 | PA | | 7-0 | 33-22-42 | | L00220 | =G | | C | * | L00219 | =G | C | | 150-199 |
| 510 | 22 | PA | | 9-0 | 33-27-11 | | D02880 | | 2 | | | SP01268 | | 9 | | 050-099 |
| 510 | 22 | PA | | 8-0 | 33-27-11 | | D02880 | | 2 | | | SP01268 | | 9 | | 150-199 |
| 510 | 22 | PA | | 6-3 | 33-27-11 | | D02880 | | 2 | | | SP01268 | | 9 | | 275-299 |
| 511 | 22 | PA | | 9-0 | 33-27-11 | | D02880 | | 3 | | | SP01266 | | 9 | | 050-099 |
| 511 | 22 | PA | | 8-0 | 33-27-11 | | D02880 | | 3 | | | SP01266 | | 9 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 96

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|---|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0818 | 286T0818 | | | AFT SIDEWALL WASH LTS,GALLEY LTS,DIRECT CLG LTS (continued) | | | | | | | | | | | | | | | |
| 511 | 22 | | PA | 6-3 | 33-27-11 | D02880 | | 3 | | | | | | SP01266 | | 9 | | | 275-299 |
| 512 | 20 | | PA | 59-0 | 33-27-11 | D02880 | | 5 | | | | | | D05120P | | 9 | | | 050-099 |
| 512 | 20 | | PA | 70-0 | 33-27-11 | D02880 | | 5 | | | | | | D05120P | | 9 | | | 150-199 |
| 512 | 20 | | PA | 70-5 | 33-27-11 | D02880 | | 5 | | | | | | D05120P | | 9 | | | 275-299 |
| 513 | 20 | | PA | 9-0 | 33-27-11 | D02880 | | 7 | | | | | | GD00070 | A.. | 2 | | | 050-099, 150-199 |
| 513 | 20 | | PA | 9-4 | 33-27-11 | D02880 | | 7 | | | | | | GD00070 | A.. | 2 | | | 275-299 |
| 514 | 20 | | PA | 6-0 | 33-27-11 | D02880 | | 8 | | | | | | L00204 | =G | E | | | 050-099 |
| 514 | 20 | | PA | 5-0 | 33-27-11 | D02880 | | 8 | | | | | | L00206 | =G | E | | | 150-157 |
| 514 | 20 | | PA | 5-0 | 33-27-11 | D02880 | | 8 | | | | | | L00206 | =G | E | * | | 162-199 |
| 514 | 20 | | PA | 4-11 | 33-27-11 | D02880 | | 8 | | | | | | L00204 | =G | E | | | 275-299 |
| 515 | 22 | | PA | 5-0 | 33-27-11 | D02880 | | 9 | | | | | | SP01258 | | 9 | | | 050-099, 150-199 |
| 515 | 22 | | PA | 4-8 | 33-27-11 | D02880 | | 9 | | | | | | SP01258 | | 9 | | | 275-299 |
| 516 | 22 | | PA | 5-0 | 33-27-11 | D02880 | | 10 | | | | | | SP01260 | | 9 | | | 050-099, 150-199 |
| 516 | 22 | | PA | 4-8 | 33-27-11 | D02880 | | 10 | | | | | | SP01260 | | 9 | | | 275-299 |
| 517 | 22 | | PA | 7-0 | 33-27-11 | D02880 | | 11 | | | | | | SP01264 | | 9 | | | 050-099 |
| 517 | 22 | | PA | 4-0 | 33-27-11 | D02880 | | 11 | | | | | | SP01264 | | 9 | | | 150-199 |
| 517 | 22 | | PA | 2-11 | 33-27-11 | D02880 | | 11 | | | | | | SP01264 | | 9 | | | 275-299 |
| 518 | 22 | | PA | 5-0 | 33-27-11 | D02880 | | 12 | | | | | | SP01262 | | 9 | | | 050-099 |
| 518 | 22 | | PA | 4-0 | 33-27-11 | D02880 | | 12 | | | | | | SP01262 | | 9 | | | 150-199 |
| 518 | 22 | | PA | 2-11 | 33-27-11 | D02880 | | 12 | | | | | | SP01262 | | 9 | | | 275-299 |
| 519 | 22 | | PA | 6-0 | 33-27-11 | D02884 | | 2 | | | | | | SP01284 | | 9 | | | 050-099 |
| 519 | 22 | | PA | 7-0 | 33-27-11 | D02884 | | 2 | | | | | | SP01284 | | 9 | | | 150-199 |
| 519 | 22 | | PA | 3-8 | 33-27-11 | D02884 | | 2 | | | | | | SP01284 | | 9 | | | 275-299 |
| 520 | 22 | | PA | 6-0 | 33-27-11 | D02884 | | 3 | | | | | | SP01282 | | 9 | | | 050-099 |
| 520 | 22 | | PA | 7-0 | 33-27-11 | D02884 | | 3 | | | | | | SP01282 | | 9 | | | 150-199 |
| 520 | 22 | | PA | 3-8 | 33-27-11 | D02884 | | 3 | | | | | | SP01282 | | 9 | | | 275-299 |
| 521 | 22 | | PA | 63-0 | 33-27-11 | D02884 | | 5 | | | | | | D05120P | | 10 | | | 050-099 |
| 521 | 22 | | PA | 73-0 | 33-27-11 | D02884 | | 5 | | | | | | D05120P | | 10 | | | 150-199 |
| 521 | 22 | | PA | 34-0 | 33-27-11 | SM00015 | | | | S | | | | D05120P | | 10 | | | 275-299 |
| 522 | 20 | | PA | 9-0 | 33-27-11 | D02884 | | 7 | | | | | | GD00932 | A.. | 2 | | | 050-099, 150-199 |
| 522 | 20 | | PA | 8-5 | 33-27-11 | D02884 | | 7 | | | | | | GD00932 | A.. | 2 | | | 275-299 |
| 523 | 22 | | PA | 14-0 | 33-27-11 | D02884 | | 8 | | | | | | L00208 | =G | E | | | 050-099 |
| 523 | 22 | | PA | 9-0 | 33-27-11 | D02884 | | 8 | | | | | | L00210 | =G | E | * | | 150-199 |
| 523 | 22 | | PA | 8-8 | 33-27-11 | D02884 | | 8 | | | | | | L00208 | =G | E | * | | 275-299 |
| 524 | 22 | | PA | 10-0 | 33-27-11 | D02884 | | 9 | | | | | | SP01274 | | 9 | | | 050-099 |
| 524 | 22 | | PA | 9-0 | 33-27-11 | D02884 | | 9 | | | | | | SP01274 | | 9 | | | 150-199 |
| 524 | 22 | | PA | 8-3 | 33-27-11 | D02884 | | 9 | | | | | | SP01274 | | 9 | | | 275-299 |
| 525 | 22 | | PA | 10-0 | 33-27-11 | D02884 | | 10 | | | | | | SP01276 | | 9 | | | 050-099 |
| 525 | 22 | | PA | 9-0 | 33-27-11 | D02884 | | 10 | | | | | | SP01276 | | 9 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 97

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|---|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0818 | 286T0818 | | | AFT SIDEWALL WASH LTS,GALLEY LTS,DIRECT CLG LTS (continued) | | | | | | | | | | | | | | | |
| 525 | 22 | PA | | | 8-3 | 33-27-11 | D02884 | | 10 | | | | | SP01276 | | 9 | | | 275-299 |
| 526 | 22 | PA | | | 10-0 | 33-27-11 | D02884 | | 11 | | | | | SP01280 | | 9 | | | 050-099 |
| 526 | 22 | PA | | | 9-0 | 33-27-11 | D02884 | | 11 | | | | | SP01280 | | 9 | | | 150-199 |
| 526 | 22 | PA | | | 8-5 | 33-27-11 | D02884 | | 11 | | | | | SP01280 | | 9 | | | 275-299 |
| 527 | 22 | PA | | | 10-0 | 33-27-11 | D02884 | | 12 | | | | | SP01278 | | 9 | | | 050-099 |
| 527 | 22 | PA | | | 9-0 | 33-27-11 | D02884 | | 12 | | | | | SP01278 | | 9 | | | 150-199 |
| 527 | 22 | PA | | | 8-5 | 33-27-11 | D02884 | | 12 | | | | | SP01278 | | 9 | | | 275-299 |
| 528 | 22 | PA | | | 9-0 | 33-27-11 | SP01262 | | | 9 | | | | SP01316 | | 9 | | | 050-099 |
| 528 | 22 | PA | | | 7-0 | 33-27-11 | SP01262 | | | 9 | | | | SP01316 | | 9 | | | 150-199 |
| 528 | 22 | PA | | | 5-3 | 33-27-11 | SP01262 | | | 9 | | | | SP01316 | | 9 | | | 275-299 |
| 529 | 22 | PA | | | 9-0 | 33-27-11 | SP01264 | | | 9 | | | | SP01314 | | 9 | | | 050-099 |
| 529 | 22 | PA | | | 7-0 | 33-27-11 | SP01264 | | | 9 | | | | SP01314 | | 9 | | | 150-199 |
| 529 | 22 | PA | | | 5-3 | 33-27-11 | SP01264 | | | 9 | | | | SP01314 | | 9 | | | 275-299 |
| 530 | 22 | PA | | | 13-0 | 33-27-11 | SP01278 | | | 9 | | | | SP01296 | | 9 | | | 050-099 |
| 530 | 22 | PA | | | 11-0 | 33-27-11 | SP01278 | | | 9 | | | | SP01296 | | 9 | | | 150-199 |
| 530 | 22 | PA | | | 10-6 | 33-27-11 | SP01278 | | | 9 | | | | SP01296 | | 9 | | | 275-299 |
| 531 | 22 | PA | | | 13-0 | 33-27-11 | SP01280 | | | 9 | | | | SP01294 | | 9 | | | 050-099 |
| 531 | 22 | PA | | | 11-0 | 33-27-11 | SP01280 | | | 9 | | | | SP01294 | | 9 | | | 150-199 |
| 531 | 22 | PA | | | 10-6 | 33-27-11 | SP01280 | | | 9 | | | | SP01294 | | 9 | | | 275-299 |
| 533 | 20 | PA | | | 12-0 | 33-27-11 | L00204 | | = G | E | | | | GD00070 | | S.. | 2 | | 050-099 |
| 533 | 20 | PA | | | 11-0 | 33-27-11 | L00206 | | = G | E | | | | GD00070 | | S.. | 2 | | 150-157 |
| 533 | 20 | PA | | | 11-0 | 33-27-11 | L00206 | | = G | E | * | | | GD00070 | | S.. | 2 | | 162-199 |
| 533 | 20 | PA | | | 10-6 | 33-27-11 | L00204 | | = G | E | | | | GD00070 | | S.. | 2 | | 275-299 |
| 535 | 20 | PA | | | 11-0 | 33-27-11 | L00208 | | = G | E | | | | GD00070 | | S.. | 2 | | 050-099 |
| 535 | 20 | PA | | | 8-0 | 33-27-11 | GD00070 | | S.. | 2 | | | | L00210 | | = G | E | * | 150-199 |
| 535 | 20 | PA | | | 7-9 | 33-27-11 | GD00070 | | S.. | 2 | | | | L00208 | | = G | E | * | 275-299 |
| 536 | 20 | PA | | | 11-0 | 33-22-42 | L01061 | | = G | C | | | | GD01120 | | A.. | 2 | | 150-199 |
| 538 | 22 | PA | | | 10-0 | 33-21-35 | SM00011 | | | 9 | | | | D11246 | | 3 | | | 150-199 |
| 538 | 22 | PA | | | 9-4 | 33-21-35 | SM00011 | | | 9 | | | | D11246 | | 3 | | | 275-299 |
| 539 | 22 | PA | | | 10-0 | 33-21-35 | SM00012 | | | 9 | | | | D11246 | | 4 | | | 150-199 |
| 539 | 22 | PA | | | 9-4 | 33-21-35 | SM00012 | | | 9 | | | | D11246 | | 4 | | | 275-299 |
| 540 | 22 | PA | | | 13-0 | 33-21-35 | D11250 | | | 9 | | | | D11246 | | 1 | | | 150-199, 275-299 |
| 541 | 22 | PA | | | 13-0 | 33-21-35 | D11250 | | | 10 | | | | D11246 | | 2 | | | 150-199, 275-299 |
| 542 | 20 | PA | | | 4-0 | 33-21-35 | D11246 | | | 5 | | | | GD04984 | | S.. | E | | 150-199 |
| 542 | 20 | PA | | | 3-4 | 33-21-35 | D11246 | | | 5 | | | | GD04984 | | S.. | E | | 275-299 |
| 543 | 22 | PA | | | 7-0 | 33-21-35 | D11252 | | | 2 | | | | D11248 | | 1 | | | 150-199 |
| 543 | 22 | PA | | | 6-9 | 33-21-35 | D11252 | | | 2 | | | | D11248 | | 1 | | | 275-299 |
| 544 | 22 | PA | | | 7-0 | 33-21-35 | D11252 | | | 3 | | | | D11248 | | 2 | | | 150-199 |
| 544 | 22 | PA | | | 6-9 | 33-21-35 | D11252 | | | 3 | | | | D11248 | | 2 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 98

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-----|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W0818 | 286T0818 | | | AFT SIDEWALL WASH LTS,GALLEY LTS,DIRECT CLG LTS (continued) | | | | | | | | | | | | | | |
| 545 | 22 | | PA | 8-0 | 33-21-35 | SM00013 | | | | 9 | | | | D11248 | 3 | | | 150-199 |
| 545 | 22 | | PA | 7-7 | 33-21-35 | SM00013 | | | | 9 | | | | D11248 | 3 | | | 275-299 |
| 546 | 22 | | PA | 8-0 | 33-21-35 | SM00014 | | | | 9 | | | | D11248 | 4 | | | 150-199 |
| 546 | 22 | | PA | 7-7 | 33-21-35 | SM00014 | | | | 9 | | | | D11248 | 4 | | | 275-299 |
| 547 | 20 | | PA | 4-0 | 33-21-35 | D11248 | | | 5 | | | | | GD04986 | S.. | E | | 150-199 |
| 547 | 20 | | PA | 3-3 | 33-21-35 | D11248 | | | 5 | | | | | GD04986 | S.. | E | | 275-299 |
| 601 | 20 | | PA | 65-0 | 33-22-42 | L00220 | | | =P | C | * | | | D05120P | 6 | | | 150-199 |
| 602 | 20 | | PA | 7-0 | 33-22-42 | L00220 | | | =P | C | * | | | L00219 | =P | C | | 150-199 |
| 603 | 20 | | PA | 46-0 | 33-22-42 | D05120P | | | 4 | | | | | L01136 | =P | C | * | 050-099 |
| 603 | 20 | | PA | 57-0 | 33-22-42 | D05120P | | | 4 | | | | | L01136 | =P | C | * | 150-199 |
| 604 | 20 | | PA | 25-0 | 33-22-42 | L01136 | | | =P | C | * | | | L01136 | =P | C | | 050-099 |
| 604 | 20 | | PA | 25-0 | 33-22-42 | L01135 | | | =P | C | | | | L01136 | =P | C | * | 150-199 |
| 605 | 20 | | PA | 25-0 | 33-22-42 | L01136 | | | =G | C | * | | | L01135 | =G | C | | 050-099, 150-199 |
| 606 | 20 | | PA | 10-0 | 33-22-42 | L01136 | | | =G | C | * | | | GD01120 | A.. | 2 | | 050-099, 150-199 |
| 607 | 20 | | PA | 10-0 | 33-22-42 | L00220 | | | =G | C | * | | | GD01120 | A.. | 2 | | 150-199 |
| 608 | 18 | | PA | 12-3 | 33-22-42 | D07082J | | | 3 | DK | | | | GD01036 | A.. | E | | 280-299 |
| 609 | 18 | | PA | 60-2 | 33-22-42 | D07082J | | | 2 | DK | | | | D05120P | 6 | | | 280-299 |
| 610 | 18 | | PA | 60-2 | 33-22-42 | D07082J | | | 1 | DK | | | | D05120P | 14 | | | 280-299 |
| 800 | 18 | | PA | 12-0 | 33-27-11 | L01138 | | | =G | C | | | | GD00070 | A.. | 2 | | 150-199 |
| 801 | 18 | | PA | 73-0 | 33-27-11 | L01138 | | | =P | C | | | | D05120P | 16 | DK | | 150-157 |
| 801 | 18 | | PA | 73-0 | 33-27-11 | L01138 | | | =P | C | * | | | D05120P | 16 | DK | | 162-199 |
| 802 | 18 | | PA | 8-0 | 33-27-11 | L01138 | | | =P | C | | | | L01140 | =P | C | | 150-157 |
| 802 | 18 | | PA | 8-0 | 33-27-11 | L01138 | | | =P | C | * | | | L01140 | =P | C | | 162-199 |
| 803 | 18 | | PA | 12-0 | 33-27-11 | L01140 | | | =G | C | | | | GD00932 | A.. | 2 | | 150-199 |
| A-A | | | | 0-0 | 33-27-11 | L00206 | | | BLK | | | | | SP01258 | 9 | | | ALL |
| A-B | | | | 0-0 | 33-27-11 | L00206 | | | BLK | | | | | SP01260 | 9 | | | ALL |
| A-C | | | | 0-0 | 33-27-11 | L00206 | | | WHT | | | | | SP01264 | 9 | | | ALL |
| A-D | | | | 0-0 | 33-27-11 | L00206 | | | WHT | | | | | SP01262 | 9 | | | ALL |
| B-A | | | | 0-0 | 33-27-11 | L00209 | | | BLK | | | | | SP01284 | 9 | | | ALL |
| B-B | | | | 0-0 | 33-27-11 | L00209 | | | BLK | | | | | SP01282 | 9 | | | ALL |
| B-C | | | | 0-0 | 33-27-11 | L00209 | | | WHT | | | | | SP01296 | 9 | | | ALL |
| B-D | | | | 0-0 | 33-27-11 | L00209 | | | WHT | | | | | SP01294 | 9 | | | ALL |
| C-A | | | | 0-0 | 33-27-11 | L00210 | | | BLK | | | | | SP01274 | 9 | | | ALL |
| C-B | | | | 0-0 | 33-27-11 | L00210 | | | BLK | | | | | SP01276 | 9 | | | ALL |
| C-C | | | | 0-0 | 33-27-11 | L00210 | | | WHT | | | | | SP01280 | 9 | | | ALL |
| C-D | | | | 0-0 | 33-27-11 | L00210 | | | WHT | | | | | SP01278 | 9 | | | ALL |
| D-A | | | | 0-0 | 33-27-11 | L00205 | | | BLK | | | | | SP01268 | 9 | | | ALL |
| D-B | | | | 0-0 | 33-27-11 | L00205 | | | BLK | | | | | SP01266 | 9 | | | ALL |
| D-C | | | | 0-0 | 33-27-11 | L00205 | | | WHT | | | | | SP01316 | 9 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 99

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0818 | 286T0818 | | | | AFT SIDEWALL WASH LTS,GALLEY LTS,DIRECT CLG LTS (continued) | | | | | | | | | | |
| D-D | | | | | 0-0 | 33-27-11 | L00205 | | WHT | | SP01314 | | 9 | | ALL |
| W0819 | 286T0819 | | | | RATCOM SYSTEM POWER & LGA SUBSYSTEM,E9,E2-3,E2-6 | | | | | | | | | | |
| 001 | 16 | | PA | | 108-4 | 23-25-11 | D06151J | | 21 | | D06149J | | 21 | | 156-157, 166-199, 277-278 |
| 001 | 16 | | PA | | 108-0 | 23-25-11 | D06151J | | 21 | | D06149J | | 21 | | 280-299 |
| 003 | 24 | | PK | | 112-2 | 23-25-14 | D06153J | | 7 | | D06149J | | 31 | | 150, 153-199, 277-278 |
| 003 | 24 | | PK | | 112-0 | 23-25-14 | D06153J | | 7 | | D06149J | | 31 | | 280-299 |
| 004 | 24 | | PK | | 112-2 | 23-25-14 | D06153J | | 8 | | D06149J | | 30 | | 150, 153-199, 277-278 |
| 004 | 24 | | PK | | 112-0 | 23-25-14 | D06153J | | 8 | | D06149J | | 30 | | 280-299 |
| 005 | 24 | | PV | AE | 112-2 | 23-25-14 | D06153J | | 10 | | D06149J | | 29 | | 277-278 |
| 005 | 24 | | PV | AE | 112-0 | 23-25-14 | D06153J | | 10 | | D06149J | | 29 | | 280-299 |
| 005Z | | | | AE | 0-0 | 23-25-14 | D06153J | | 9 | | D06149J | | 28 | | 277-299 |
| 006 | 24 | | PV | AF | 112-2 | 23-25-14 | D06153J | | 11 | | D06149J | | 27 | | 277-278 |
| 006 | 24 | | PV | AF | 112-0 | 23-25-14 | D06153J | | 11 | | D06149J | | 27 | | 280-299 |
| 006Z | | | | AF | 0-0 | 23-25-14 | D06153J | | 12 | | D06149J | | 26 | | 277-299 |
| 007 | 24 | | PK | | 112-2 | 23-25-14 | D06153J | | 13 | | D06149J | | 25 | | 150, 153-199, 277-278 |
| 007 | 24 | | PK | | 112-0 | 23-25-14 | D06153J | | 13 | | D06149J | | 25 | | 280-299 |
| 008 | 22 | | PA | | 108-4 | 23-25-13 | D06149J | | 13 | | D06151J | | 7 | | 150, 153-155, 162-165 |
| 008 | 24 | | PK | | 108-4 | 23-25-13 | D06149J | | 13 | | D06151J | | 7 | | 156-157, 166-199, 277-278 |
| 008 | 24 | | PK | | 108-0 | 23-25-13 | D06149J | | 13 | | D06151J | | 7 | | 280-299 |
| 202B | 22 | | PR | IB | 112-2 | 23-25-13 | D06149J | | 3 | | D06153J | | 3 | | 150, 153-155, 162-165 |
| 202B | 24 | | PW | IB | 112-2 | 23-25-13 | D06149J | | 3 | | D06153J | | 3 | | 156-157, 166-199, 277-278 |
| 202B | 24 | | PW | IB | 112-0 | 23-25-13 | D06149J | | 3 | | D06153J | | 3 | | 280-299 |
| 202R | 22 | | PR | IB | 0-0 | 23-25-13 | D06149J | | 2 | | D06153J | | 2 | | 150, 153-155, 162-165 |
| 202R | 24 | | PW | IB | 0-0 | 23-25-13 | D06149J | | 2 | | D06153J | | 2 | | 156-157, 166-199, 277-299 |
| 202Z | | | | IB | 0-0 | 23-25-13 | D06149J | | 1 | | D06153J | | 1 | | 150, 153-199, 277-299 |
| 203B | 22 | | PR | IC | 112-2 | 23-25-13 | D06149J | | 34 | | D06153J | | 6 | | 150, 153-155, 162-165 |
| 203B | 24 | | PW | IC | 112-2 | 23-25-13 | D06149J | | 34 | | D06153J | | 6 | | 156-157, 166-199, 277-278 |
| 203B | 24 | | PW | IC | 112-0 | 23-25-13 | D06149J | | 34 | | D06153J | | 6 | | 280-299 |
| 203R | 22 | | PR | IC | 0-0 | 23-25-13 | D06149J | | 33 | | D06153J | | 5 | | 150, 153-155, 162-165 |
| 203R | 24 | | PW | IC | 0-0 | 23-25-13 | D06149J | | 33 | | D06153J | | 5 | | 156-157, 166-199, 277-299 |
| 203Z | | | | IC | 0-0 | 23-25-13 | D06149J | | 32 | | D06153J | | 4 | | 150, 153-199, 277-299 |
| 204B | 22 | | PR | ID | 108-4 | 23-25-13 | D06149J | | 4 | | D06151J | | 3 | | 150, 153-155, 162-165 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 100

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-------|---|---------|-------|------|------|--------|-------|---------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0819 | 286T0819 | | | | RATCOM SYSTEM POWER & LGA SUBSYSTEM,E9,E2-3,E2-6 (continued) | | | | | | | | | | |
| 204B | 24 | PW | ID | 108-4 | 23-25-13 | D06149J | | 4 | | | | D06151J | 3 | | 156-157, 166-199, 277-278 |
| 204B | 24 | PW | ID | 108-0 | 23-25-13 | D06149J | | 4 | | | | D06151J | 3 | | 280-299 |
| 204R | 22 | PR | ID | 0-0 | 23-25-13 | D06149J | | 6 | | | | D06151J | 2 | | 150, 153-155, 162-165 |
| 204R | 24 | PW | ID | 0-0 | 23-25-13 | D06149J | | 6 | | | | D06151J | 2 | | 156-157, 166-199, 277-299 |
| 204Z | | | ID | 0-0 | 23-25-13 | D06149J | | 5 | | | | D06151J | 1 | | 150, 153-199, 277-299 |
| 205B | 22 | PR | IE | 108-4 | 23-25-13 | D06149J | | 12 | | | | D06151J | 6 | | 150, 153-155, 162-165 |
| 205B | 24 | PW | IE | 108-4 | 23-25-13 | D06149J | | 12 | | | | D06151J | 6 | | 156-157, 166-199, 277-278 |
| 205B | 24 | PW | IE | 108-0 | 23-25-13 | D06149J | | 12 | | | | D06151J | 6 | | 280-299 |
| 205R | 22 | PR | IE | 0-0 | 23-25-13 | D06149J | | 11 | | | | D06151J | 5 | | 150, 153-155, 162-165 |
| 205R | 24 | PW | IE | 0-0 | 23-25-13 | D06149J | | 11 | | | | D06151J | 5 | | 156-157, 166-199, 277-299 |
| 205Z | | | IE | 0-0 | 23-25-13 | D06149J | | 10 | | | | D06151J | 4 | | 150, 153-199, 277-299 |
| 206B | 24 | PW | IF | 108-4 | 23-25-13 | D06149J | | 16 | | | | D06151J | 10 | | 150, 153-199, 277-278 |
| 206B | 24 | PW | IF | 108-0 | 23-25-13 | D06149J | | 16 | | | | D06151J | 10 | | 280-299 |
| 206R | 24 | PW | IF | 0-0 | 23-25-13 | D06149J | | 15 | | | | D06151J | 9 | | 150, 153-199, 277-299 |
| 206Z | | | IF | 0-0 | 23-25-13 | D06149J | | 14 | | | | D06151J | 8 | | 150, 153-199, 277-299 |
| 207B | 24 | PW | IG | 108-4 | 23-25-13 | D06149J | | 19 | | | | D06151J | 13 | | 156-157, 166-199, 277-278 |
| 207B | 24 | PW | IG | 108-0 | 23-25-13 | D06149J | | 19 | | | | D06151J | 13 | | 280-299 |
| 207R | 24 | PW | IG | 0-0 | 23-25-13 | D06149J | | 18 | | | | D06151J | 12 | | 156-157, 166-199, 277-299 |
| 207Z | | | IG | 0-0 | 23-25-13 | D06149J | | 17 | | | | D06151J | 11 | | 156-157, 166-199, 277-299 |
| 208B | 24 | PW | IH | 108-4 | 23-25-13 | D06149J | | 24 | | | | D06151J | 16 | | 156-157, 166-199, 277-278 |
| 208B | 24 | PW | IH | 108-0 | 23-25-13 | D06149J | | 24 | | | | D06151J | 16 | | 280-299 |
| 208R | 24 | PW | IH | 0-0 | 23-25-13 | D06149J | | 22 | | | | D06151J | 15 | | 156-157, 166-199, 277-299 |
| 208Z | | | IH | 0-0 | 23-25-13 | D06149J | | 20 | | | | D06151J | 14 | | 156-157, 166-199, 277-299 |
| 911 | 22 | PA | | 112-2 | 23-25-14 | D06149J | | 7 | | | | D06153J | 15 | | 150, 153-199 |
| 914B | 22 | PR | HX | 112-2 | 23-25-14 | D06149J | | 28 | | | | D06153J | 9 | | 150, 153-199 |
| 914R | 22 | PR | HX | 0-0 | 23-25-14 | D06149J | | 29 | | | | D06153J | 10 | | 150, 153-199 |
| 914Z | | | HX | 0-0 | 23-25-14 | D06149J | | DED | | | | D06153J | REF | HX | 150, 153-199 |
| 915B | 22 | PR | HW | 112-2 | 23-25-14 | D06149J | | 26 | | | | D06153J | 12 | | 150, 153-199 |
| 915R | 22 | PR | HW | 0-0 | 23-25-14 | D06149J | | 27 | | | | D06153J | 11 | | 150, 153-199 |

WIRE LIST

D280T132

91-21-11

Section W0810

Page 101

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | | |
|-------------------|--------------------|----|----|---|-------|----------|-------------|------|------|-----------|---------|------|------|--------|-------------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0819 | 286T0819 | | | RATCOM SYSTEM POWER & LGA SUBSYSTEM,E9,E2-3,E2-6 (continued) | | | | | | | | | | | | |
| 915Z | | | | HW | 0-0 | 23-25-14 | D06149J | | DED | | D06153J | | REF | | HX | 150, 153-199 |
| FRX | | | | | 0-0 | 23-25-14 | D06153J | | 14 | | D06153J | | REF | | HX | 150, 153-199 |

WIRE LIST
D280T132

91-21-11
Section W0810
Page 102 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0820 | 286T0820 | | | L FWD LAV | | | | | | | | | | | | | |
| 001 | 20 | | PA | 17-0 | 33-26-21 | D05160P | 12 | | | | | | D00808 | 13 | | | 050-099, 150-199 |
| 001 | 20 | | PA | 21-0 | 33-26-21 | L00425 | S | C | * | | | | D00808 | 13 | | | 275-278 |
| 001 | 20 | | PA | 20-5 | 33-26-21 | D05160P | 25 | | | | | | D00808 | 13 | | | 280-299 |
| 003 | 20 | | PA | 25-0 | 33-26-21 | L00425 | P | C | * | | | | SM00005 | | S | | 050-099 |
| 003 | 22 | | PA | 23-0 | 33-26-21 | SM00005 | | | | | | | L00425 | P | C | * | 150-199 |
| 004 | 20 | | PA | 16-0 | 33-26-21 | L00425 | P | C | * | | | | D05160P | 4 | | | 050-099 |
| 004 | 22 | | PA | 16-0 | 33-26-21 | L00425 | P | C | * | | | | D05160P | 4 | | | 150-199 |
| 004 | 22 | | PA | 12-0 | 33-26-21 | L00425 | P | C | * | | | | D05160P | 4 | | | 275-278 |
| 004 | 22 | | PA | 12-5 | 33-26-21 | L00425 | P | C | * | | | | D05160P | 4 | | | 280-299 |
| 005 | 20 | | PA | 17-0 | 33-26-21 | L00399 | G | C | | | | | GD00119 | A.. | 2 | | 050-099 |
| 005 | 20 | | PA | 16-0 | 33-26-21 | L00399 | G | C | | | | | GD00119 | A.. | 2 | | 150-199 |
| 005 | 20 | | PA | 11-0 | 33-26-21 | D06100J | 1 | | | | | | GD00119 | A.. | 2 | | 275-299 |
| 007 | 18 | | PA | 0-6 | 33-26-11 | D00808 | 6 | | | | | | SM00001 | | 9 | | ALL |
| 008 | 22 | | PA | 17-0 | 33-26-11 | D00808 | 15 | | | | | | D05160P | 8 | | | 050-099, 150-199, 275-278 |
| 008 | 22 | | PA | 17-5 | 33-26-11 | D00808 | 15 | | | | | | D05160P | 8 | | | 280-299 |
| 009 | 20 | | PA | 17-0 | 33-26-11 | D00808 | 17 | | | | | | D05160P | 15 | | | 050-099, 150-199, 275-278 |
| 009 | 20 | | PA | 17-5 | 33-26-11 | D00808 | 17 | | | | | | D05160P | 15 | | | 280-299 |
| 010 | 16 | | PA | 5-0 | 38-13-11 | D00808 | 2 | | | | | | GD00002 | A.. | 2 | | ALL |
| 011 | 20 | | PA | 5-0 | 33-26-11 | D00808 | 1 | | | | | | GD00002 | A.. | 2 | | ALL |
| 012 | 18 | | PA | 0-6 | 33-26-21 | D00808 | 10 | | | | | | SM00005 | | S | | 050-099 |
| 012 | 18 | | PA | 4-0 | 33-26-21 | D00808 | 10 | | | | | | SM00005 | | S | | 150-199 |
| 012 | 20 | | PA | 17-0 | 33-26-21 | D00808 | 10 | | | | | | D05160P | 12 | | | 275-278 |
| 012 | 20 | | PA | 17-5 | 33-26-21 | D00808 | 10 | | | | | | D05160P | 12 | | | 280-299 |
| 013 | 16 | | PA | 17-0 | 38-13-11 | D00808 | 8 | | | | | | D05160P | 23 | FL | | 050-099 |
| 013 | 16 | | PA | 17-0 | 38-13-11 | D00808 | 8 | | | | | | D05160P | 23 | | | 150-199, 275-278 |
| 013 | 16 | | PA | 17-5 | 38-13-11 | D00808 | 8 | | | | | | D05160P | 23 | | | 280-299 |
| 014 | 22 | | PA | 17-0 | 33-25-11 | D00808 | 7 | | | | | | D05160P | 10 | | | 050-099 |
| 014 | 22 | | PA | 4-0 | 33-25-11 | D00808 | 7 | | | | | | B00144 | HI | C | | 150-199 |
| 014 | 22 | | PA | 8-0 | 33-25-11 | D00808 | 7 | | | | | | B00144 | HI | C | * | 275-299 |
| 015 | 22 | | PA | 17-0 | 33-25-11 | D00808 | 9 | | | | | | D05160P | 11 | | | 050-099, 150-199, 275-278 |
| 015 | 22 | | PA | 17-5 | 33-25-11 | D00808 | 9 | | | | | | D05160P | 11 | | | 280-299 |
| 016 | 22 | | PA | 13-0 | 33-25-11 | D05160P | 28 | | | | | | SP03700 | | S | | 050-099 |
| 016 | 22 | | PA | 12-0 | 33-25-11 | SP03700 | | | | S | | | D05160P | 28 | | | 150-199 |
| 016 | 22 | | PA | 22-0 | 33-25-11 | D00808 | 25 | | | | | | SP00568 | | S | | 275-299 |
| 017 | 20 | | PA | 5-0 | 33-25-11 | D00808 | 26 | | | | | | GD00002 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0820 | 286T0820 | | | L FWD LAV (continued) | | | | | | | | | | | |
| 018 | 18 | | PA | | 17-0 | 38-32-12 | D00808 | 20 | DK | | D05160P | 3 | DL | | 050-099, 150-156, 162-165, 275-276 |
| 018 | 18 | | PA | | 17-0 | 38-32-16 | D00808 | 20 | DK | | D05160P | 3 | DL | | 157, 166-199, 277-278 |
| 018 | 18 | | PA | | 17-5 | 38-32-16 | D00808 | 20 | DK | | D05160P | 3 | DL | | 280-299 |
| 019 | 22 | | PA | | 17-0 | 38-32-12 | D00808 | 21 | | | D05160P | 2 | | | 050-099, 275-276 |
| 019 | 20 | | PA | | 17-0 | 38-32-12 | D00808 | 21 | | | D05160P | 2 | | | 150-156, 162-165 |
| 019 | 20 | | PA | | 17-0 | 38-32-16 | D00808 | 21 | | | D05160P | 2 | | | 157, 166-199 |
| 019 | 22 | | PA | | 17-0 | 38-32-16 | D00808 | 21 | | | D05160P | 2 | | | 277-278 |
| 019 | 22 | | PA | | 17-5 | 38-32-16 | D00808 | 21 | | | D05160P | 2 | | | 280-299 |
| 020 | 20 | | PA | | 5-0 | 38-32-12 | D00808 | 18 | | | GD00002 | D.. | 2 | | 050-099, 150-156, 162-165, 275-276 |
| 020 | 20 | | PA | | 5-0 | 38-32-16 | D00808 | 18 | | | GD00002 | D.. | 2 | | 157, 166-199, 277-299 |
| 021 | 20 | | PA | | 5-0 | 38-32-12 | D00808 | 19 | | | GD00002 | S.. | 2 | | 050-099, 150-156, 162-165, 275-276 |
| 021 | 20 | | PA | | 5-0 | 38-32-16 | D00808 | 19 | | | GD00002 | S.. | 2 | | 157, 166-199, 277-299 |
| 024 | 20 | | PA | | 17-0 | 33-24-11 | D00808 | 12 | | | D05160P | 1 | | | 050-099, 150-199, 275-278 |
| 024 | 20 | | PA | | 17-5 | 33-24-11 | D00808 | 12 | | | D05160P | 1 | | | 280-299 |
| 025 | 20 | | PA | | 27-0 | 33-26-21 | L00425 | S | C | * | L00399 | S | C | | 050-099 |
| 025 | 22 | | PA | | 26-0 | 33-26-21 | L00399 | S | C | | L00425 | S | C | * | 150-199 |
| 025 | 22 | | PA | | 16-0 | 33-26-21 | L00425 | S | C | * | D06100J | 5 | | | 275-299 |
| 026 | 20 | | PA | | 27-0 | 33-26-21 | L00425 | P | C | * | L00399 | P | C | | 050-099 |
| 026 | 22 | | PA | | 26-0 | 33-26-21 | L00425 | P | C | * | L00399 | P | C | | 150-199 |
| 026 | 22 | | PA | | 16-0 | 33-26-21 | L00425 | P | C | * | D06100J | 4 | | | 275-299 |
| 027 | 20 | | PA | | 14-0 | SPARE | L00425 | G | C | | GD00119 | A.. | 2 | | 150-199 |
| 027 | 20 | | PA | | 10-0 | 33-26-21 | L00425 | G | C | | GD00119 | A.. | 2 | | 275-299 |
| 031 | 20 | | PA | | 17-0 | 33-24-11 | D00808 | 30 | | | D05160P | 13 | | | 050-099, 275-276 |
| 031 | 20 | | PA | | 17-0 | 33-24-11 | SP00002 | | S | | D00808 | 30 | | | 150, 152-199 |
| 031 | 20 | | PA | | 17-0 | 33-24-11 | D05160P | 13 | | | D00808 | 30 | | | 151 |
| 031 | 20 | | PQ | BF | 17-0 | 33-24-11 | D00808 | 30 | | | D05160P | 13 | | | 277-278 |
| 031 | 20 | | PQ | BF | 17-5 | 33-24-11 | D00808 | 30 | | | D05160P | 13 | | | 280-299 |
| 031Z | | | | BF | 0-0 | 33-24-11 | D00808 | DED | | | D05160P | DED | | | 277-299 |
| 032 | 20 | | PA | | 17-0 | 33-24-11 | D00808 | 32 | | | D05160P | 14 | | | 050-099, 275-276 |
| 032 | 20 | | PA | | 17-0 | 33-24-11 | SP00001 | | 9 | | D00808 | 32 | | | 150, 152-199 |
| 032 | 20 | | PA | | 17-0 | 33-24-11 | D05160P | 14 | | | D00808 | 32 | | | 151 |
| 032 | 20 | | PQ | BG | 17-0 | 33-24-11 | D00808 | 32 | | | D05160P | 14 | | | 277-278 |
| 032 | 20 | | PQ | BG | 17-5 | 33-24-11 | D00808 | 32 | | | D05160P | 14 | | | 280-299 |
| 032Z | | | | BG | 0-0 | 33-24-11 | D00808 | DED | | | D05160P | DED | | | 277-299 |
| 035 | 20 | | PA | | 14-0 | 33-26-21 | L00425 | G | C | | GD00119 | A.. | 2 | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0820 | 286T0820 | | | L FWD LAV (continued) | | | | | | | | | | | | | | |
| 036 | 22 | | PA | 17-0 | 33-26-11 | SM00001 | | | | 9 | | | | D05160P | 7 | | | 050-099, 275-278 |
| 036 | 22 | | PA | 15-0 | 33-26-11 | SM00001 | | | | 9 | | | | D05160P | 7 | | | 150-199 |
| 036 | 22 | | PA | 17-5 | 33-26-11 | SM00001 | | | | 9 | | | | D05160P | 7 | | | 280-299 |
| 037 | 20 | | PA | 12-0 | 33-26-21 | L00425 | | | S | C | * | | | D05160P | 16 | | | 275-278 |
| 037 | 20 | | PA | 12-5 | 33-26-21 | L00425 | | | S | C | * | | | D05160P | 16 | | | 280-299 |
| 039 | 22 | | PA | 16-0 | 33-25-11 | D05160P | | | | 10 | | | | B00144 | HI | C | * | 275-278 |
| 039 | 22 | | PA | 16-5 | 33-25-11 | D05160P | | | | 10 | | | | B00144 | HI | C | * | 280-299 |
| 045 | 20 | | PA | 18-0 | 25-42-11 | D13478 | | | | 19 | | | | D05160P | 31 | | | 050-099, 150-199 |
| 045 | 20 | | PA | 17-0 | 25-42-11 | D00808 | | | | 29 | | | | D05160P | 31 | | | 275-278 |
| 045 | 20 | | PA | 17-5 | 25-42-11 | D00808 | | | | 29 | | | | D05160P | 31 | | | 280-299 |
| 059 | 22 | | PA | 13-0 | 33-25-11 | D05160P | | | | 24 | | | | SP00568 | | S | | 050-099 |
| 059 | 22 | | PA | 12-0 | 33-25-11 | D05160P | | | | 24 | | | | SP00568 | | S | | 150-199 |
| 060 | 22 | | PA | 17-0 | 33-25-11 | D00808 | | | | 25 | | | | D05160P | 26 | | | 050-099 |
| 060 | 22 | | PA | 17-0 | 33-25-11 | D05160P | | | | 26 | | | | D00808 | 25 | | | 150-199 |
| 066 | 20 | | PA | 16-0 | 33-26-21 | L00425 | | | S | C | * | | | D05160P | 16 | | | 050-099 |
| 066 | 20 | | PA | 16-0 | 33-26-21 | D05160P | | | | 16 | | | | L00425 | S | C | * | 150-199 |
| 073 | 20 | | PA | 18-0 | 26-13-12 | D13478 | | | | 5 | | | | D05160P | 9 | | | 050-099, 162-199 |
| 076 | 20 | | PA | 18-0 | 26-13-12 | D13478 | | | | 13 | | | | D05160P | 33 | | | 050-099 |
| 076 | 20 | | PA | 18-0 | 26-13-12 | D05160P | | | | 33 | | | | D13478 | 13 | | | 162-199 |
| 080 | 20 | | PA | 18-0 | 26-13-12 | D13478 | | | | 1 | | | | D05160P | 27 | | | 050-099 |
| 080 | 20 | | PA | 18-0 | 26-13-12 | D05160P | | | | 27 | | | | D13478 | 1 | | | 162-199 |
| 081 | 20 | | PA | 13-0 | 26-13-12 | D05160P | | | | 34 | | | | SP03606 | | 9 | | 162-199 |
| 082 | 20 | | PA | 13-0 | 26-13-12 | SP03608 | | | | 9 | | | | D05160P | 22 | | | 162-199 |
| 083 | 20 | | PA | 13-0 | 26-13-12 | SP03604 | | | | 9 | | | | D05160P | 20 | | | 162-199 |
| 100 | 20 | | PA | 18-0 | 26-13-11 | D13478 | | | | 10 | | | | D05160P | 29 | | | 050-099 |
| 100 | 20 | | PA | 18-0 | 26-13-11 | D05160P | | | | 29 | | | | D13478 | 10 | | | 150-157 |
| 100 | 18 | | PA | 18-0 | 26-13-11 | D05160P | | | | 29 | DL | | | D13478 | 10 | DK | | 162-199 |
| 101 | 20 | | PA | 18-0 | 26-13-11 | D13478 | | | | 20 | | | | D05160P | 30 | | | 050-099 |
| 101 | 20 | | PA | 18-0 | 26-13-11 | D05160P | | | | 30 | | | | D13478 | 20 | | | 150-199 |
| 102 | 20 | | PA | 18-0 | 26-13-11 | D13478 | | | | 11 | | | | D05160P | 17 | | | 050-099 |
| 102 | 20 | | PA | 28-0 | 26-13-11 | SP03598 | | | | | S | | | D13478 | 11 | | | 150-157 |
| 102 | 20 | | PA | 28-0 | 26-13-11 | SP03598 | | | | 9 | | | | D13478 | 11 | | | 162-199 |
| 103 | 20 | | PA | 18-0 | 26-13-11 | D13478 | | | | 12 | | | | D05160P | 18 | | | 050-099 |
| 103 | 20 | | PA | 28-0 | 26-13-11 | SP03600 | | | | | S | | | D13478 | 12 | | | 150-157 |
| 103 | 20 | | PA | 28-0 | 26-13-11 | SP03600 | | | | 9 | | | | D13478 | 12 | | | 162-199 |
| 104 | 20 | | PA | 18-0 | 26-13-11 | D13478 | | | | 23 | | | | D05160P | 19 | | | 050-099 |
| 104 | 20 | | PA | 28-0 | 26-13-11 | SP03602 | | | | 9 | | | | D13478 | 23 | | | 150-199 |
| 105 | 20 | | PA | 18-0 | 26-13-11 | D13478 | | | | 22 | | | | D05160P | 20 | | | 050-099 |
| 105 | 20 | | PA | 28-0 | 26-13-11 | SP03604 | | | | 9 | | | | D13478 | 22 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0820 | 286T0820 | | | L FWD LAV (continued) | | | | | | | | | | | |
| 106 | 20 | | PA | | 18-0 | 26-13-11 | D13478 | | 9 | | D05160P | | 34 | | 050-099 |
| 106 | 20 | | PA | | 28-0 | 26-13-11 | SP03606 | | 9 | | D13478 | | 9 | | 150-199 |
| 107 | 20 | | PA | | 18-0 | 26-13-11 | D13478 | | 7 | | D05160P | | 22 | | 050-099 |
| 107 | 20 | | PA | | 28-0 | 26-13-11 | SP03608 | | 9 | | D13478 | | 7 | | 150-199 |
| 108 | 20 | | PA | | 7-0 | 26-13-11 | D13478 | | 21 | | GD00002 | S.. | 2 | | 050-099, 150-199 |
| 109 | 20 | | PA | | 7-0 | 26-13-11 | D13478 | | 8 | | GD00002 | D.. | 2 | | 050-099, 150-199 |
| 201B | 22 | | PB | A | 15-0 | 23-31-14 | D00808 | | 5 | | SM00002 | | S | | 050-099, 275-299 |
| 201B | 22 | | PB | A | 14-0 | 23-31-14 | D00808 | | 5 | | SM00002 | | S | | 150-199 |
| 201R | 22 | | PB | A | 0-0 | 23-31-14 | D00808 | | 16 | | SM00003 | | S | | ALL |
| 202B | 22 | | PB | B | 3-0 | 23-31-14 | SM00002 | | | S | D05160P | | 6 | | 050-099, 275-278 |
| 202B | 22 | | PB | B | 4-0 | 23-31-14 | SM00002 | | | S | D05160P | | 6 | | 150-199 |
| 202B | 22 | | PB | B | 3-5 | 23-31-14 | SM00002 | | | S | D05160P | | 6 | | 280-299 |
| 202R | 22 | | PB | B | 0-0 | 23-31-14 | SM00003 | | | S | D05160P | | 5 | | ALL |
| 203B | 22 | | PB | C | 8-0 | 23-31-14 | B00246 | COM | Z | | SM00002 | | S | | 275-299 |
| 203R | 22 | | PB | C | 0-0 | 23-31-14 | B00246 | 4K | Z | | SM00003 | | S | | 275-299 |
| 204B | 22 | | PB | D | 10-0 | 23-31-14 | SM00002 | | | S | B00289 | COM | Z | | 050-099 |
| 204B | 22 | | PB | D | 4-0 | 23-31-14 | B00289 | COM | Z | | SM00002 | | S | | 150-199 |
| 204B | 22 | | PB | D | 11-0 | 23-31-14 | B00289 | COM | Z | | SM00002 | | S | | 275-299 |
| 204R | 22 | | PB | D | 0-0 | 23-31-14 | SM00003 | | | S | B00289 | 4K | Z | | 050-099 |
| 204R | 22 | | PB | D | 0-0 | 23-31-14 | B00289 | 4K | Z | | SM00003 | | S | | 150-199, 275-299 |
| 205B | 22 | | PB | E | 20-0 | 23-31-14 | B00293 | COM | Z | | SM00002 | | S | | 150-157 |
| 205B | 22 | | PB | E | 12-0 | 23-31-14 | B00293 | COM | Z | | SM00002 | | S | | 162-199 |
| 205R | 22 | | PB | E | 0-0 | 23-31-14 | B00293 | 4K | Z | | SM00003 | | S | | 150-199 |
| 900 | 20 | | PA | | 17-0 | 33-24-11 | SP00001 | | 9 | | D05160P | | 14 | | 150, 152-156, 162-199 |
| 900 | 20 | | PA | | 17-0 | 33-32-21 | SP00001 | | 9 | | D05160P | | 14 | | 157 |
| 901 | 20 | | PA | | 17-0 | 33-24-11 | SP00002 | | S | | D05160P | | 13 | | 150, 152-156, 162-199 |
| 901 | 20 | | PA | | 17-0 | 33-32-21 | SP00002 | | S | | D05160P | | 13 | | 157 |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING | | | | | | | | | | | |
| 017 | 22 | | PA | | 25-0 | 33-22-42 | D05914P | | 1 | | D06148J | | 5 | | 275-299 |
| 018 | 22 | | PA | | 25-0 | 33-22-42 | D05914P | | 2 | | D06148J | | 2 | | 275-299 |
| 030 | 20 | | PA | | 5-0 | 33-22-42 | D06148J | | 3 | | GD04198 | A.. | 2 | | 275-299 |
| 037 | 20 | | PA | | 5-0 | 33-22-42 | GD04198 | | S.. | 2 | D06148J | | 1 | | 275-299 |
| 038 | 20 | | PA | | 29-0 | 33-21-11 | D05912P | | 6 | | D11162 | | 5 | | 150-199, 275-278 |
| 038 | 20 | | PA | | 22-0 | 33-21-11 | D05912P | | 6 | | D07096J | | 1 | | 280-299 |
| 039 | 20 | | PA | | 43-0 | 33-21-11 | D05914P | | 8 | | SM00004 | | 9 | | 150-199 |
| 039 | 20 | | PA | | 71-0 | 33-21-11 | D05914P | | 8 | | D07096J | | 9 | | 280-299 |
| 040 | 20 | | PA | | 19-0 | 33-21-11 | D02748 | | 2 | | SP00824 | | 9 | | 050-099 |
| 040 | 20 | | PA | | 21-0 | 33-21-11 | D02748 | | 2 | | SP00824 | | 9 | | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | | |
| 040 | 20 | | PA | 17-0 | 33-21-11 | D02748 | | 2 | | | | | SP00824 | | 9 | | 280-299 |
| 041 | 20 | | PA | 19-0 | 33-21-11 | D02748 | | 3 | | | | | SP00826 | | 9 | | 050-099 |
| 041 | 20 | | PA | 21-0 | 33-21-11 | D02748 | | 3 | | | | | SP00826 | | 9 | | 150-199, 275-278 |
| 041 | 20 | | PA | 17-0 | 33-21-11 | D02748 | | 3 | | | | | SP00826 | | 9 | | 280-299 |
| 042 | 20 | | PA | 3-0 | 33-21-11 | D02748 | | 5 | | | | | SM00002 | | 9 | | 050-099 |
| 042 | 20 | | PA | 21-0 | 33-21-11 | D02748 | | 5 | | | | | D05912P | | 5 | | 150-199, 275-299 |
| 043 | 20 | | PA | 6-0 | 33-21-11 | D02748 | | 7 | | | | | GD01930 | A.. | 2 | | 050-099, 150-199, 275-278 |
| 043 | 20 | | PA | 14-0 | 33-21-11 | D02748 | | 7 | | | | | GD01920 | A.. | 2 | | 280-299 |
| 044 | 20 | | PA | 6-0 | 33-21-11 | D02748 | | 8 | | | | | GD01930 | S.. | 2 | | 050-099, 150-199, 275-278 |
| 044 | 20 | | PA | 14-0 | 33-21-11 | D02748 | | 8 | | | | | GD01920 | S.. | 2 | | 280-299 |
| 045 | 20 | | PA | 8-0 | 33-21-11 | D02748 | | 9 | | | | | SP00828 | | 9 | | 050-099, 150-199, 275-278 |
| 045 | 20 | | PA | 5-0 | 33-21-11 | D02748 | | 9 | | | | | SP00828 | | 9 | | 280-299 |
| 046 | 20 | | PA | 8-0 | 33-21-11 | D02748 | | 10 | | | | | SP00830 | | 9 | | 050-099, 150-199, 275-278 |
| 046 | 20 | | PA | 5-0 | 33-21-11 | D02748 | | 10 | | | | | SP00830 | | 9 | | 280-299 |
| 047 | 20 | | PA | 8-0 | 33-21-11 | D02748 | | 11 | | | | | SP00832 | | 9 | | 050-099, 150-199, 275-278 |
| 047 | 20 | | PA | 5-0 | 33-21-11 | D02748 | | 11 | | | | | SP00832 | | 9 | | 280-299 |
| 048 | 20 | | PA | 8-0 | 33-21-11 | D02748 | | 12 | | | | | SP00834 | | 9 | | 050-099, 150-199, 275-278 |
| 048 | 20 | | PA | 5-0 | 33-21-11 | D02748 | | 12 | | | | | SP00834 | | 9 | | 280-299 |
| 049 | 20 | | PA | 24-0 | 33-21-11 | SP00820 | | | 9 | | | | SP00832 | | 9 | | 050-099 |
| 049 | 20 | | PA | 25-0 | 33-21-11 | SP00820 | | | 9 | | | | SP00832 | | 9 | | 150-199, 275-278 |
| 049 | 20 | | PA | 19-0 | 33-21-11 | SP00820 | | | 9 | | | | SP00832 | | 9 | | 280-299 |
| 050 | 20 | | PA | 24-0 | 33-21-11 | SP00822 | | | 9 | | | | SP00834 | | 9 | | 050-099 |
| 050 | 20 | | PA | 25-0 | 33-21-11 | SP00822 | | | 9 | | | | SP00834 | | 9 | | 150-199, 275-278 |
| 050 | 20 | | PA | 19-0 | 33-21-11 | SP00822 | | | 9 | | | | SP00834 | | 9 | | 280-299 |
| 051 | 20 | | PA | 8-0 | 33-21-11 | SP01990 | | | S | | | | GD01930 | S.. | 2 | | 050-099, 150-199, 275-278 |
| 051 | 20 | | PA | 16-0 | 33-21-11 | SP01990 | | | S | | | | GD01920 | S.. | 2 | | 280-299 |
| 052 | 20 | | PA | 15-0 | 33-21-11 | D02750 | | 2 | | | | | SP00840 | | 9 | | 050-099 |
| 052 | 20 | | PA | 17-0 | 33-21-13 | D02750 | | 2 | | | | | SP00840 | | 9 | | 150-199, 275-278 |
| 053 | 20 | | PA | 15-0 | 33-21-11 | D02750 | | 3 | | | | | SP00842 | | 9 | | 050-099 |
| 053 | 20 | | PA | 17-0 | 33-21-13 | D02750 | | 3 | | | | | SP00842 | | 9 | | 150-199, 275-278 |
| 054 | 20 | | PA | 3-0 | 33-21-11 | D02750 | | 5 | | | | | SM00002 | | 9 | | 050-099 |
| 054 | 20 | | PA | 41-0 | 33-21-13 | D02750 | | 5 | | | | | D05912P | | 4 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|-----|---|--|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | | | | | |
| 054 | 20 | | PA | 30-0 | 33-21-13 | D02750 | | 5 | | | | | | | D05914P | 10 | | | | 275-278 |
| 054 | 20 | | PA | 71-0 | 33-21-11 | D07096J | | 6 | | | | | | | D05914P | 10 | | | | 280-299 |
| 055 | 20 | | PA | 6-0 | 33-21-11 | D02750 | | 7 | | | | | | | GD01930 | A.. | 2 | | | 050-099 |
| 055 | 20 | | PA | 10-0 | 33-21-13 | D02750 | | 7 | | | | | | | GD00960 | A.. | 2 | | | 150-199 |
| 055 | 20 | | PA | 8-0 | 33-21-13 | D02750 | | 7 | | | | | | | GD01940 | A.. | 2 | | | 275-278 |
| 056 | 20 | | PA | 5-0 | 33-21-11 | D02750 | | 8 | | | | | | | GD01930 | S.. | 2 | | | 050-099 |
| 056 | 20 | | PA | 10-0 | 33-21-13 | D02750 | | 8 | | | | | | | GD00960 | S.. | 2 | | | 150-199 |
| 056 | 20 | | PA | 8-0 | 33-21-13 | D02750 | | 8 | | | | | | | GD01940 | S.. | 2 | | | 275-278 |
| 057 | 20 | | PA | 19-0 | 33-21-11 | D02750 | | 9 | | | | | | | SP00844 | | 9 | | | 050-099 |
| 057 | 20 | | PA | 18-0 | 33-21-13 | D02750 | | 9 | | | | | | | SP00844 | | 9 | | | 150-199, 275-278 |
| 058 | 20 | | PA | 19-0 | 33-21-11 | D02750 | | 10 | | | | | | | SP00846 | | 9 | | | 050-099 |
| 058 | 20 | | PA | 18-0 | 33-21-13 | D02750 | | 10 | | | | | | | SP00846 | | 9 | | | 150-199, 275-278 |
| 059 | 20 | | PA | 19-0 | 33-21-11 | D02750 | | 11 | | | | | | | SP00848 | | 9 | | | 050-099 |
| 059 | 20 | | PA | 18-0 | 33-21-13 | D02750 | | 11 | | | | | | | SP00848 | | 9 | | | 150-199, 275-278 |
| 060 | 20 | | PA | 19-0 | 33-21-11 | D02750 | | 12 | | | | | | | SP00850 | | 9 | | | 050-099 |
| 060 | 20 | | PA | 18-0 | 33-21-13 | D02750 | | 12 | | | | | | | SP00850 | | 9 | | | 150-199, 275-278 |
| 061 | 20 | | PA | 27-0 | 33-21-11 | SP00836 | | | 9 | | | | | | SP00848 | | 9 | | | 050-099 |
| 061 | 20 | | PA | 28-0 | 33-21-13 | SP00836 | | | 9 | | | | | | SP00848 | | 9 | | | 150-199, 275-278 |
| 062 | 20 | | PA | 27-0 | 33-21-11 | SP00838 | | | 9 | | | | | | SP00850 | | 9 | | | 050-099 |
| 062 | 20 | | PA | 28-0 | 33-21-13 | SP00838 | | | 9 | | | | | | SP00850 | | 9 | | | 150-199, 275-278 |
| 063 | 20 | | PA | 8-0 | 33-21-11 | SP01994 | | | S | | | | | | GD04444 | S.. | 2 | | | 050-099 |
| 063 | 20 | | PA | 6-0 | 33-21-13 | SP01994 | | | S | | | | | | GD00960 | S.. | 2 | | | 150-199 |
| 063 | 20 | | PA | 16-0 | 33-21-13 | SP01994 | | | S | | | | | | GD01940 | S.. | 2 | | | 275-278 |
| 065 | 20 | | PA | 17-0 | 33-21-11 | D02736 | | 2 | | | | | | | D06098P | | 4 | | | 275-278 |
| 065 | 20 | | PA | 14-0 | 33-21-11 | D02736 | | 2 | | | | | | | D06098P | | 4 | | | 280-299 |
| 066 | 20 | | PA | 17-0 | 33-21-11 | D02736 | | 3 | | | | | | | D06098P | | 5 | | | 275-278 |
| 066 | 20 | | PA | 14-0 | 33-21-11 | D02736 | | 3 | | | | | | | D06098P | | 5 | | | 280-299 |
| 067 | 20 | | PA | 11-0 | 33-21-11 | D02736 | | 5 | | | | | | | D05912P | | 3 | | | 275-278 |
| 067 | 20 | | PA | 10-0 | 33-21-11 | D02736 | | 5 | | | | | | | D05912P | | 3 | | | 280-299 |
| 068 | 20 | | PA | 6-0 | 33-21-11 | D02736 | | 7 | | | | | | | GD01920 | A.. | 2 | | | 275-299 |
| 069 | 20 | | PA | 6-0 | 33-21-11 | D02736 | | 8 | | | | | | | GD01920 | S.. | 2 | | | 275-299 |
| 070 | 20 | | PA | 9-0 | 33-21-11 | D02736 | | 9 | | | | | | | SP00898 | | 9 | | | 275-278 |
| 070 | 20 | | PA | 6-0 | 33-21-11 | D02736 | | 9 | | | | | | | SP00898 | | 9 | | | 280-299 |
| 071 | 20 | | PA | 9-0 | 33-21-11 | D02736 | | 10 | | | | | | | SP00900 | | 9 | | | 275-278 |
| 071 | 20 | | PA | 6-0 | 33-21-11 | D02736 | | 10 | | | | | | | SP00900 | | 9 | | | 280-299 |
| 072 | 20 | | PA | 9-0 | 33-21-11 | D02736 | | 11 | | | | | | | SP00902 | | 9 | | | 275-278 |
| 072 | 20 | | PA | 6-0 | 33-21-11 | D02736 | | 11 | | | | | | | SP00902 | | 9 | | | 280-299 |
| 073 | 20 | | PA | 9-0 | 33-21-11 | D02736 | | 12 | | | | | | | SP00904 | | 9 | | | 275-278 |
| 073 | 20 | | PA | 6-0 | 33-21-11 | D02736 | | 12 | | | | | | | SP00904 | | 9 | | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|---|----------|---------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | | | |
| 074 | 20 | PA | | 20-0 | 33-21-11 | D06098P | | 2 | | | | | | | SP00902 | 9 | | 275-278 |
| 074 | 20 | PA | | 13-0 | 33-21-11 | D06098P | | 2 | | | | | | | SP00902 | 9 | | 280-299 |
| 075 | 20 | PA | | 20-0 | 33-21-11 | D06098P | | 3 | | | | | | | SP00904 | 9 | | 275-278 |
| 075 | 20 | PA | | 13-0 | 33-21-11 | D06098P | | 3 | | | | | | | SP00904 | 9 | | 280-299 |
| 076 | 20 | PA | | 8-0 | 33-21-11 | L00232 | | =G | E | | | | | | GD01918 | S.. | 2 | 275-278 |
| 076 | 20 | PA | | 6-0 | 33-21-11 | L00232 | | =G | E | | | | | | GD01918 | S.. | 2 | 280-299 |
| 077 | 20 | PA | | 10-0 | 33-21-11 | D06098P | | 1 | | | | | | | GD01916 | S.. | 2 | 275-278 |
| 077 | 20 | PA | | 7-0 | 33-21-11 | D06098P | | 1 | | | | | | | GD01916 | S.. | 2 | 280-299 |
| 078 | 20 | PA | | 15-0 | 33-21-11 | D02740 | | 2 | | | | | | | SP00910 | 9 | | 050-099 |
| 078 | 20 | PA | | 16-0 | 33-21-11 | D02740 | | 2 | | | | | | | SP00910 | 9 | | 150-199, 275-278 |
| 078 | 20 | PA | | 12-0 | 33-21-11 | D02740 | | 2 | | | | | | | SP00910 | 9 | | 280-299 |
| 079 | 20 | PA | | 15-0 | 33-21-11 | D02740 | | 3 | | | | | | | SP00912 | 9 | | 050-099 |
| 079 | 20 | PA | | 16-0 | 33-21-11 | D02740 | | 3 | | | | | | | SP00912 | 9 | | 150-199, 275-278 |
| 079 | 20 | PA | | 12-0 | 33-21-11 | D02740 | | 3 | | | | | | | SP00912 | 9 | | 280-299 |
| 080 | 20 | PA | | 11-0 | 33-21-11 | D02740 | | 5 | | | | | | | D05912P | 7 | | 050-099 |
| 080 | 20 | PA | | 12-0 | 33-21-11 | D02740 | | 5 | | | | | | | D05912P | 7 | | 150-199, 275-299 |
| 081 | 20 | PA | | 6-0 | 33-21-11 | D02740 | | 7 | | | | | | | GD01920 | A.. | 2 | 050-099 |
| 081 | 20 | PA | | 5-0 | 33-21-11 | D02740 | | 7 | | | | | | | GD01920 | A.. | 2 | 150-199, 275-299 |
| 082 | 20 | PA | | 9-0 | 33-21-11 | D02740 | | 8 | | | | | | | GD01924 | S.. | 2 | 050-099, 280-299 |
| 082 | 20 | PA | | 8-0 | 33-21-11 | D02740 | | 8 | | | | | | | GD01924 | S.. | 2 | 150-199, 275-278 |
| 083 | 20 | PA | | 12-0 | 33-21-11 | D02740 | | 9 | | | | | | | SP00914 | 9 | | 050-099 |
| 083 | 20 | PA | | 11-0 | 33-21-11 | D02740 | | 9 | | | | | | | SP00914 | 9 | | 150-199, 275-278 |
| 083 | 20 | PA | | 8-0 | 33-21-11 | D02740 | | 9 | | | | | | | SP00914 | 9 | | 280-299 |
| 084 | 20 | PA | | 12-0 | 33-21-11 | D02740 | | 10 | | | | | | | SP00916 | 9 | | 050-099 |
| 084 | 20 | PA | | 11-0 | 33-21-11 | D02740 | | 10 | | | | | | | SP00916 | 9 | | 150-199, 275-278 |
| 084 | 20 | PA | | 8-0 | 33-21-11 | D02740 | | 10 | | | | | | | SP00916 | 9 | | 280-299 |
| 085 | 20 | PA | | 12-0 | 33-21-11 | D02740 | | 11 | | | | | | | SP00918 | 9 | | 050-099 |
| 085 | 20 | PA | | 11-0 | 33-21-11 | D02740 | | 11 | | | | | | | SP00918 | 9 | | 150-199, 275-278 |
| 085 | 20 | PA | | 8-0 | 33-21-11 | D02740 | | 11 | | | | | | | SP00918 | 9 | | 280-299 |
| 086 | 20 | PA | | 12-0 | 33-21-11 | D02740 | | 12 | | | | | | | SP00920 | 9 | | 050-099 |
| 086 | 20 | PA | | 11-0 | 33-21-11 | D02740 | | 12 | | | | | | | SP00920 | 9 | | 150-199, 275-278 |
| 086 | 20 | PA | | 8-0 | 33-21-11 | D02740 | | 12 | | | | | | | SP00920 | 9 | | 280-299 |
| 087 | 20 | PA | | 23-0 | 33-21-11 | SP00906 | | | | | | | | | SP00918 | 9 | | 050-099, 150-199, 275-278 |
| 087 | 20 | PA | | 16-0 | 33-21-11 | SP00906 | | | | | | | | | SP00918 | 9 | | 280-299 |
| 088 | 20 | PA | | 23-0 | 33-21-11 | SP00908 | | | | | | | | | SP00920 | 9 | | 050-099, 150-199, 275-278 |
| 088 | 20 | PA | | 16-0 | 33-21-11 | SP00908 | | | | | | | | | SP00920 | 9 | | 280-299 |
| 089 | 20 | PA | | 8-0 | 33-21-11 | SP02000 | | | | | | | | | GD01924 | S.. | 2 | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | | |
| 089 | 20 | PA | | 7-0 | 33-21-11 | SP02000 | | | | S | | | | GD01924 | S.. | 2 | 150-199, 275-278 |
| 089 | 20 | PA | | 5-0 | 33-21-11 | SP02000 | | | | S | | | | GD01924 | S.. | 2 | 280-299 |
| 090 | 20 | PA | | 10-0 | 33-21-11 | SP02002 | | | | S | | | | GD01918 | S.. | 2 | 050-099 |
| 090 | 20 | PA | | 11-0 | 33-21-11 | SP02002 | | | | S | | | | GD01918 | S.. | 2 | 150-199, 275-278 |
| 090 | 20 | PA | | 7-0 | 33-21-11 | SP02002 | | | | S | | | | GD01918 | S.. | 2 | 280-299 |
| 091 | 20 | PA | | 11-0 | 33-21-11 | SP01992 | | | | S | | | | GD01924 | S.. | 2 | 050-099 |
| 091 | 20 | PA | | 13-0 | 33-21-11 | SP01992 | | | | S | | | | GD01924 | S.. | 2 | 150-199, 275-278 |
| 091 | 20 | PA | | 9-0 | 33-21-11 | SP01992 | | | | S | | | | GD01924 | S.. | 2 | 280-299 |
| 092 | 20 | PA | | 11-0 | 33-21-11 | SP01996 | | | | S | | | | GD01930 | S.. | 2 | 050-099 |
| 092 | 20 | PA | | 13-0 | 33-21-13 | SP01996 | | | | S | | | | GD04874 | S.. | 2 | 150-199 |
| 092 | 20 | PA | | 11-0 | 33-21-13 | SP01996 | | | | S | | | | GD00960 | S.. | 2 | 275-278 |
| 094 | 20 | PA | | 22-0 | 33-21-11 | L00763 | | | = G | E | | | | GD00960 | S.. | 2 | 150-199 |
| 094 | 20 | PA | | 13-0 | 33-21-11 | SP04052 | | | | 9 | | | | GD04874 | S.. | 2 | 275-277 |
| 094 | 20 | PA | | 13-0 | 33-21-11 | L00763 | | | = G | E | | | | GD04874 | S.. | 2 | 278 |
| 095 | 20 | PA | | 13-0 | 33-21-13 | D02758 | | | | 2 | | | | SP01394 | | 9 | 050-099 |
| 095 | 20 | PA | | 16-0 | 33-21-13 | D02758 | | | | 2 | | | | SP01394 | | 9 | 150-199, 275-278 |
| 095 | 20 | PA | | 10-0 | 33-21-13 | D02758 | | | | 2 | | | | SP01394 | | 9 | 280-299 |
| 096 | 20 | PA | | 13-0 | 33-21-13 | D02758 | | | | 3 | | | | SP01396 | | 9 | 050-099 |
| 096 | 20 | PA | | 16-0 | 33-21-13 | D02758 | | | | 3 | | | | SP01396 | | 9 | 150-199, 275-278 |
| 096 | 20 | PA | | 10-0 | 33-21-13 | D02758 | | | | 3 | | | | SP01396 | | 9 | 280-299 |
| 097 | 20 | PA | | 15-0 | 33-21-13 | D02758 | | | | 5 | | | | SM00002 | | 9 | 050-099 |
| 097 | 20 | PA | | 33-0 | 33-21-13 | D02758 | | | | 5 | | | | D05914P | 4 | | 150-199 |
| 097 | 20 | PA | | 28-0 | 33-21-13 | D02758 | | | | 5 | | | | D05914P | 4 | | 275-278 |
| 097 | 20 | PA | | 26-0 | 33-21-13 | D02758 | | | | 5 | | | | D05914P | 4 | | 280-299 |
| 098 | 20 | PA | | 4-0 | 33-21-13 | D02758 | | | | 7 | | | | GD04444 | A.. | 2 | 050-099 |
| 098 | 20 | PA | | 12-0 | 33-21-13 | D02758 | | | | 7 | | | | GD01748 | A.. | 2 | 150-199 |
| 098 | 20 | PA | | 9-0 | 33-21-13 | D02758 | | | | 7 | | | | GD01940 | A.. | 2 | 275-278 |
| 098 | 20 | PA | | 5-0 | 33-21-13 | D02758 | | | | 7 | | | | GD01940 | A.. | 2 | 280-299 |
| 099 | 20 | PA | | 4-0 | 33-21-13 | D02758 | | | | 8 | | | | GD04444 | S.. | 2 | 050-099 |
| 099 | 20 | PA | | 12-0 | 33-21-13 | D02758 | | | | 8 | | | | GD01748 | S.. | 2 | 150-199 |
| 099 | 20 | PA | | 9-0 | 33-21-13 | D02758 | | | | 8 | | | | GD01940 | S.. | 2 | 275-278 |
| 099 | 20 | PA | | 5-0 | 33-21-13 | D02758 | | | | 8 | | | | GD01940 | S.. | 2 | 280-299 |
| 100 | 20 | PA | | 17-0 | 33-21-13 | D02758 | | | | 9 | | | | SP01386 | | 9 | 050-099 |
| 100 | 20 | PA | | 12-0 | 33-21-13 | D02758 | | | | 9 | | | | SP01386 | | 9 | 150-199, 275-299 |
| 101 | 20 | PA | | 17-0 | 33-21-13 | D02758 | | | | 10 | | | | SP01388 | | 9 | 050-099 |
| 101 | 20 | PA | | 12-0 | 33-21-13 | D02758 | | | | 10 | | | | SP01388 | | 9 | 150-199, 275-299 |
| 102 | 20 | PA | | 17-0 | 33-21-13 | D02758 | | | | 11 | | | | SP01390 | | 9 | 050-099 |
| 102 | 20 | PA | | 12-0 | 33-21-13 | D02758 | | | | 11 | | | | SP01390 | | 9 | 150-199, 275-299 |
| 103 | 20 | PA | | 17-0 | 33-21-13 | D02758 | | | | 12 | | | | SP01392 | | 9 | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W0820
Page 8
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | | |
| 103 | 20 | | PA | 12-0 | 33-21-13 | D02758 | | 12 | | | | | SP01392 | | 9 | | 150-199, 275-299 |
| 104 | 20 | | PA | 14-0 | 33-21-13 | SP02004 | | | S | | | | GD01940 | S.. | 2 | | 050-099 |
| 104 | 20 | | PA | 22-0 | 33-21-13 | SP02004 | | | S | | | | GD01748 | S.. | 2 | | 150-199 |
| 104 | 20 | | PA | 8-0 | 33-21-13 | SP02004 | | | S | | | | GD04198 | S.. | 2 | | 275-299 |
| 105 | 20 | | PA | 21-0 | 33-21-13 | SP02006 | | | S | | | | GD01940 | S.. | 2 | | 050-099 |
| 105 | 20 | | PA | 20-0 | 33-21-13 | SP02006 | | | S | | | | GD01748 | S.. | 2 | | 150-199 |
| 105 | 20 | | PA | 11-0 | 33-21-13 | SP02006 | | | S | | | | GD01940 | S.. | 2 | | 275-278 |
| 105 | 20 | | PA | 7-0 | 33-21-13 | SP02006 | | | S | | | | GD01940 | S.. | 2 | | 280-299 |
| 106 | 20 | | PA | 27-0 | 33-21-13 | SP01390 | | | 9 | | | | SP01398 | | 9 | | 050-099 |
| 106 | 20 | | PA | 20-0 | 33-21-13 | SP01390 | | | 9 | | | | SP01398 | | 9 | | 150-199, 275-278 |
| 106 | 20 | | PA | 17-0 | 33-21-13 | SP01390 | | | 9 | | | | SP01398 | | 9 | | 280-299 |
| 107 | 20 | | PA | 27-0 | 33-21-13 | SP01392 | | | 9 | | | | SP01400 | | 9 | | 050-099 |
| 107 | 20 | | PA | 20-0 | 33-21-13 | SP01392 | | | 9 | | | | SP01400 | | 9 | | 150-199, 275-278 |
| 107 | 20 | | PA | 17-0 | 33-21-13 | SP01392 | | | 9 | | | | SP01400 | | 9 | | 280-299 |
| 108 | 20 | | PA | 20-0 | 33-21-13 | D02978 | | 2 | | | | | SP01410 | | 9 | | 050-099 |
| 108 | 20 | | PA | 15-0 | 33-21-13 | D02978 | | 2 | | | | | SP01410 | | 9 | | 150-199 |
| 108 | 20 | | PA | 22-0 | 33-21-13 | D02978 | | 2 | | | | | SP01410 | | 9 | | 275-299 |
| 109 | 20 | | PA | 20-0 | 33-21-13 | D02978 | | 3 | | | | | SP01412 | | 9 | | 050-099 |
| 109 | 20 | | PA | 15-0 | 33-21-13 | D02978 | | 3 | | | | | SP01412 | | 9 | | 150-199 |
| 109 | 20 | | PA | 22-0 | 33-21-13 | D02978 | | 3 | | | | | SP01412 | | 9 | | 275-299 |
| 110 | 20 | | PA | 7-0 | 33-21-13 | D02978 | | 5 | | | | | SM00003 | | 9 | | 050-099 |
| 110 | 20 | | PA | 5-0 | 33-21-13 | D02978 | | 5 | | | | | SM00003 | | 9 | | 150-199 |
| 110 | 20 | | PA | 20-0 | 33-21-13 | D02978 | | 5 | | | | | SM00003 | | 9 | | 275-278 |
| 110 | 20 | | PA | 6-0 | 33-21-13 | D02978 | | 5 | | | | | SM00003 | | 9 | | 280-299 |
| 111 | 20 | | PA | 4-0 | 33-21-13 | D02978 | | 7 | | | | | GD01940 | A.. | 2 | | 050-099 |
| 111 | 20 | | PA | 10-0 | 33-21-13 | D02978 | | 7 | | | | | GD01950 | A.. | 2 | | 150-199 |
| 111 | 20 | | PA | 4-0 | 33-21-13 | D02978 | | 7 | | | | | GD01944 | A.. | 2 | | 275-278 |
| 111 | 20 | | PA | 5-0 | 33-21-13 | D02978 | | 7 | | | | | GD01944 | A.. | 2 | | 280-299 |
| 112 | 20 | | PA | 4-0 | 33-21-13 | D02978 | | 8 | | | | | GD01940 | S.. | 2 | | 050-099 |
| 112 | 20 | | PA | 10-0 | 33-21-13 | D02978 | | 8 | | | | | GD01950 | S.. | 2 | | 150-199 |
| 112 | 20 | | PA | 4-0 | 33-21-13 | D02978 | | 8 | | | | | GD01944 | S.. | 2 | | 275-278 |
| 112 | 20 | | PA | 5-0 | 33-21-13 | D02978 | | 8 | | | | | GD01944 | S.. | 2 | | 280-299 |
| 113 | 20 | | PA | 23-0 | 33-21-13 | D02978 | | 9 | | | | | SP01402 | | 9 | | 050-099 |
| 113 | 20 | | PA | 12-0 | 33-21-13 | D02978 | | 9 | | | | | SP01402 | | 9 | | 150-199 |
| 113 | 20 | | PA | 8-0 | 33-21-13 | D02978 | | 9 | | | | | SP01402 | | 9 | | 275-299 |
| 114 | 20 | | PA | 23-0 | 33-21-13 | D02978 | | 10 | | | | | SP01404 | | 9 | | 050-099 |
| 114 | 20 | | PA | 12-0 | 33-21-13 | D02978 | | 10 | | | | | SP01404 | | 9 | | 150-199 |
| 114 | 20 | | PA | 8-0 | 33-21-13 | D02978 | | 10 | | | | | SP01404 | | 9 | | 275-299 |
| 115 | 20 | | PA | 23-0 | 33-21-13 | D02978 | | 11 | | | | | SP01406 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|--|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | | | | |
| 115 | 20 | PA | | 12-0 | 33-21-13 | D02978 | | 11 | | | | | | SP01406 | | 9 | | | 150-199 |
| 115 | 20 | PA | | 8-0 | 33-21-13 | D02978 | | 11 | | | | | | SP01406 | | 9 | | | 275-299 |
| 116 | 20 | PA | | 23-0 | 33-21-13 | D02978 | | 12 | | | | | | SP01408 | | 9 | | | 050-099 |
| 116 | 20 | PA | | 12-0 | 33-21-13 | D02978 | | 12 | | | | | | SP01408 | | 9 | | | 150-199 |
| 116 | 20 | PA | | 8-0 | 33-21-13 | D02978 | | 12 | | | | | | SP01408 | | 9 | | | 275-299 |
| 117 | 20 | PA | | 10-0 | 33-21-13 | SP02008 | | | S | | | | | GD01944 | S.. | 2 | | | 050-099 |
| 117 | 20 | PA | | 7-0 | 33-21-13 | SP02008 | | | S | | | | | GD01950 | S.. | 2 | | | 150-199 |
| 117 | 20 | PA | | 11-0 | 33-21-13 | SP02008 | | | S | | | | | GD01944 | S.. | 2 | | | 275-278 |
| 117 | 20 | PA | | 8-0 | 33-21-13 | SP02008 | | | S | | | | | GD01944 | S.. | 2 | | | 280-299 |
| 118 | 20 | PA | | 11-0 | 33-21-13 | SP02010 | | | S | | | | | GD04198 | S.. | 2 | | | 050-099 |
| 118 | 20 | PA | | 17-0 | 33-21-13 | SP02010 | | | S | | | | | GD04198 | S.. | 2 | | | 150-199, 275-278 |
| 118 | 20 | PA | | 10-0 | 33-21-13 | SP02010 | | | S | | | | | GD04198 | S.. | 2 | | | 280-299 |
| 119 | 20 | PA | | 27-0 | 33-21-13 | SP01406 | | | 9 | | | | | SP01414 | | 9 | | | 050-099 |
| 119 | 20 | PA | | 25-0 | 33-21-13 | SP01406 | | | 9 | | | | | SP01414 | | 9 | | | 150-199, 275-299 |
| 120 | 20 | PA | | 27-0 | 33-21-13 | SP01408 | | | 9 | | | | | SP01416 | | 9 | | | 050-099 |
| 120 | 20 | PA | | 25-0 | 33-21-13 | SP01408 | | | 9 | | | | | SP01416 | | 9 | | | 150-199, 275-299 |
| 121 | 20 | PA | | 19-0 | 33-21-13 | D00754 | | 2 | | | | | | SP01426 | | 9 | | | 050-099, 150-199 |
| 121 | 20 | PA | | 15-0 | 33-21-13 | D00754 | | 2 | | | | | | SP01426 | | 9 | | | 275-299 |
| 122 | 20 | PA | | 19-0 | 33-21-13 | D00754 | | 3 | | | | | | SP01428 | | 9 | | | 050-099, 150-199 |
| 122 | 20 | PA | | 15-0 | 33-21-13 | D00754 | | 3 | | | | | | SP01428 | | 9 | | | 275-299 |
| 123 | 20 | PA | | 15-0 | 33-21-13 | D00754 | | 5 | | | | | | SM00003 | | 9 | | | 050-099 |
| 123 | 20 | PA | | 10-0 | 33-21-13 | D00754 | | 5 | | | | | | SM00003 | | 9 | | | 150-199 |
| 123 | 20 | PA | | 8-0 | 33-21-13 | D00754 | | 5 | | | | | | SM00003 | | 9 | | | 275-299 |
| 124 | 20 | PA | | 6-0 | 33-21-13 | D00754 | | 7 | | | | | | GD01748 | A.. | 2 | | | 050-099 |
| 124 | 20 | PA | | 8-0 | 33-21-13 | D00754 | | 7 | | | | | | GD04198 | A.. | 2 | | | 150-199 |
| 124 | 20 | PA | | 5-0 | 33-21-13 | D00754 | | 7 | | | | | | GD01950 | A.. | 2 | | | 275-299 |
| 125 | 20 | PA | | 6-0 | 33-21-13 | D00754 | | 8 | | | | | | GD01748 | S.. | 2 | | | 050-099 |
| 125 | 20 | PA | | 8-0 | 33-21-13 | D00754 | | 8 | | | | | | GD04198 | S.. | 2 | | | 150-199 |
| 125 | 20 | PA | | 5-0 | 33-21-13 | D00754 | | 8 | | | | | | GD01950 | S.. | 2 | | | 275-299 |
| 126 | 20 | PA | | 9-0 | 33-21-13 | D00754 | | 9 | | | | | | SP01418 | | 9 | | | 050-099 |
| 126 | 20 | PA | | 12-0 | 33-21-13 | D00754 | | 9 | | | | | | SP01418 | | 9 | | | 150-199, 275-299 |
| 127 | 20 | PA | | 9-0 | 33-21-13 | D00754 | | 10 | | | | | | SP01420 | | 9 | | | 050-099 |
| 127 | 20 | PA | | 12-0 | 33-21-13 | D00754 | | 10 | | | | | | SP01420 | | 9 | | | 150-199, 275-299 |
| 128 | 20 | PA | | 9-0 | 33-21-13 | D00754 | | 11 | | | | | | SP01422 | | 9 | | | 050-099 |
| 128 | 20 | PA | | 12-0 | 33-21-13 | D00754 | | 11 | | | | | | SP01422 | | 9 | | | 150-199, 275-299 |
| 129 | 20 | PA | | 9-0 | 33-21-13 | D00754 | | 12 | | | | | | SP01424 | | 9 | | | 050-099 |
| 129 | 20 | PA | | 12-0 | 33-21-13 | D00754 | | 12 | | | | | | SP01424 | | 9 | | | 150-199, 275-299 |
| 130 | 20 | PA | | 8-0 | 33-21-13 | SP02012 | | | S | | | | | GD01748 | S.. | 2 | | | 050-099 |
| 130 | 20 | PA | | 12-0 | 33-21-13 | SP02012 | | | S | | | | | GD04198 | S.. | 2 | | | 150-199 |

WIRE LIST

D280T132

91-21-11
Section W0820
Page 10
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | | |
| 130 | 20 | PA | | 8-0 | 33-21-13 | SP02012 | | | | S | | | | GD01952 | S.. | 2 | 275-299 |
| 131 | 20 | PA | | 13-0 | 33-21-13 | SP02014 | | | | S | | | | GD01950 | S.. | 2 | 050-099 |
| 131 | 20 | PA | | 12-0 | 33-21-13 | SP02014 | | | | S | | | | GD01940 | S.. | 2 | 150-199 |
| 131 | 20 | PA | | 9-0 | 33-21-13 | SP02014 | | | | S | | | | GD02544 | S.. | 2 | 275-278 |
| 131 | 20 | PA | | 8-0 | 33-21-13 | SP02014 | | | | S | | | | GD02544 | S.. | 2 | 280-299 |
| 132 | 20 | PA | | 25-0 | 33-21-13 | SP01422 | | | | 9 | | | | SP01430 | | 9 | 050-099 |
| 132 | 20 | PA | | 24-0 | 33-21-13 | SP01422 | | | | 9 | | | | SP01430 | | 9 | 150-199, 275-299 |
| 133 | 20 | PA | | 25-0 | 33-21-13 | SP01424 | | | | 9 | | | | SP01432 | | 9 | 050-099 |
| 133 | 20 | PA | | 24-0 | 33-21-13 | SP01424 | | | | 9 | | | | SP01432 | | 9 | 150-199, 275-299 |
| 134 | 20 | PA | | 18-0 | 33-21-13 | D00424 | | | 2 | | | | | SP01442 | | 9 | 050-099 |
| 135 | 20 | PA | | 18-0 | 33-21-13 | D00424 | | | 3 | | | | | SP01444 | | 9 | 050-099 |
| 136 | 20 | PA | | 15-0 | 33-21-13 | D00424 | | | 5 | | | | | D05914P | | 4 | 050-099 |
| 137 | 20 | PA | | 5-0 | 33-21-13 | D00424 | | | 7 | | | | | GD01950 | A.. | 2 | 050-099 |
| 138 | 20 | PA | | 5-0 | 33-21-13 | D00424 | | | 8 | | | | | GD01950 | S.. | 2 | 050-099 |
| 139 | 20 | PA | | 8-0 | 33-21-13 | D00424 | | | 9 | | | | | SP01434 | | 9 | 050-099 |
| 140 | 20 | PA | | 8-0 | 33-21-13 | D00424 | | | 10 | | | | | SP01436 | | 9 | 050-099 |
| 141 | 20 | PA | | 8-0 | 33-21-13 | D00424 | | | 11 | | | | | SP01438 | | 9 | 050-099 |
| 142 | 20 | PA | | 8-0 | 33-21-13 | D00424 | | | 12 | | | | | SP01440 | | 9 | 050-099 |
| 143 | 20 | PA | | 8-0 | 33-21-13 | SP02016 | | | | S | | | | GD01950 | S.. | 2 | 050-099 |
| 144 | 20 | PA | | 12-0 | 33-21-13 | SP02018 | | | | S | | | | GD01944 | S.. | 2 | 050-099 |
| 145 | 20 | PA | | 20-0 | 33-21-13 | SP01438 | | | 9 | | | | | SP01446 | | 9 | 050-099 |
| 146 | 20 | PA | | 20-0 | 33-21-13 | SP01440 | | | 9 | | | | | SP01448 | | 9 | 050-099 |
| 156 | 20 | PA | | 6-0 | 33-21-13 | SM00003 | | | 9 | | | | | D05914P | | 3 | 050-099 |
| 156 | 20 | PA | | 14-0 | 33-21-13 | SM00003 | | | 9 | | | | | D05914P | | 3 | 150-199 |
| 156 | 20 | PA | | 13-0 | 33-21-13 | SM00003 | | | 9 | | | | | D05914P | | 3 | 275-299 |
| 162 | 20 | PA | | 19-0 | 33-21-11 | D11166 | | | 5 | | | | | SM00004 | | 9 | 150-199 |
| 162 | 20 | PA | | 32-0 | 33-21-11 | D11166 | | | 5 | | | | | D05912P | | 4 | 275-278 |
| 162 | 20 | PA | | 22-0 | 33-21-11 | D07096J | | | 12 | | | | | D05912P | | 4 | 280-299 |
| 163 | 20 | PA | | 4-0 | 33-21-11 | D11170 | | | 5 | | | | | SM00004 | | 9 | 150-199 |
| 164 | 20 | PA | | 17-0 | 33-21-11 | SP02880 | | | 9 | | | | | SP02898 | | 9 | 150-199 |
| 165 | 20 | PA | | 17-0 | 33-21-11 | SP02882 | | | 9 | | | | | SP02896 | | 9 | 150-199 |
| 166 | 20 | PA | | 22-0 | 33-21-11 | SP02884 | | | 9 | | | | | SP02894 | | 9 | 150-199 |
| 166 | 20 | PA | | 20-0 | 33-21-11 | SP02884 | | | 9 | | | | | SP02894 | | 9 | 275-278 |
| 167 | 20 | PA | | 22-0 | 33-21-11 | SP02886 | | | 9 | | | | | SP02892 | | 9 | 150-199 |
| 167 | 20 | PA | | 20-0 | 33-21-11 | SP02886 | | | 9 | | | | | SP02892 | | 9 | 275-278 |
| 168 | 20 | PA | | 12-0 | 33-21-11 | SP02856 | | | | S | | | | GD01930 | S.. | 2 | 150-199, 275-278 |
| 181 | 20 | PA | | 20-0 | 33-21-11 | D11162 | | | 3 | | | | | SP02858 | | 9 | 150-199, 275-278 |
| 182 | 20 | PA | | 20-0 | 33-21-11 | D11162 | | | 2 | | | | | SP02860 | | 9 | 150-199, 275-278 |
| 183 | 20 | PA | | 5-0 | 33-21-11 | D11162 | | | 7 | | | | | GD04874 | A.. | 2 | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | | |
| 184 | 20 | PA | | 5-0 | 33-21-11 | D11162 | | 8 | | | | | GD04874 | S.. | 2 | | 150-199, 275-278 |
| 185 | 20 | PA | | 7-0 | 33-21-11 | D11162 | | 12 | | | | | SP02862 | | 9 | | 150-199, 275-278 |
| 186 | 20 | PA | | 7-0 | 33-21-11 | D11162 | | 11 | | | | | SP02864 | | 9 | | 150-199, 275-278 |
| 187 | 20 | PA | | 7-0 | 33-21-11 | D11162 | | 9 | | | | | SP02868 | | 9 | | 150-199, 275-278 |
| 188 | 20 | PA | | 7-0 | 33-21-11 | D11162 | | 10 | | | | | SP02870 | | 9 | | 150-199, 275-278 |
| 189 | 20 | PA | | 21-0 | 33-21-11 | D11166 | | 2 | | | | | SP02852 | | 9 | | 150-199 |
| 189 | 20 | PA | | 16-0 | 33-21-11 | D11166 | | 2 | | | | | SP02852 | | 9 | | 275-278 |
| 190 | 20 | PA | | 19-0 | 33-21-11 | D11166 | | 3 | | | | | SP02854 | | 9 | | 150-199 |
| 190 | 20 | PA | | 16-0 | 33-21-11 | D11166 | | 3 | | | | | SP02854 | | 9 | | 275-278 |
| 191 | 20 | PA | | 8-0 | 33-21-11 | D11166 | | 7 | | | | | GD04444 | A.. | 2 | | 150-199 |
| 191 | 20 | PA | | 6-0 | 33-21-11 | D11166 | | 7 | | | | | GD04876 | A.. | 2 | | 275-278 |
| 192 | 20 | PA | | 8-0 | 33-21-11 | D11166 | | 11 | | | | | SP02894 | | 9 | | 150-199, 275-278 |
| 193 | 20 | PA | | 8-0 | 33-21-11 | D11166 | | 12 | | | | | SP02892 | | 9 | | 150-199, 275-278 |
| 194 | 20 | PA | | 8-0 | 33-21-11 | D11166 | | 8 | | | | | GD04444 | S.. | 2 | | 150-199 |
| 194 | 20 | PA | | 6-0 | 33-21-11 | D11166 | | 8 | | | | | GD04876 | S.. | 2 | | 275-278 |
| 195 | 20 | PA | | 8-0 | 33-21-11 | D11166 | | 10 | | | | | SP02872 | | 9 | | 150-199, 275-278 |
| 196 | 20 | PA | | 8-0 | 33-21-11 | D11166 | | 9 | | | | | SP02874 | | 9 | | 150-199, 275-278 |
| 501 | 20 | PA | | 13-0 | 33-21-11 | D11170 | | 2 | | | | | SP02848 | | 9 | | 150-199 |
| 502 | 20 | PA | | 13-0 | 33-21-11 | D11170 | | 3 | | | | | SP02850 | | 9 | | 150-199 |
| 503 | 20 | PA | | 9-0 | 33-21-11 | D11170 | | 12 | | | | | SP02898 | | 9 | | 150-199 |
| 504 | 20 | PA | | 9-0 | 33-21-11 | D11170 | | 11 | | | | | SP02896 | | 9 | | 150-199 |
| 505 | 20 | PA | | 6-0 | 33-21-11 | D11170 | | 8 | | | | | GD01940 | S.. | 2 | | 150-199 |
| 506 | 20 | PA | | 9-0 | 33-21-11 | D11170 | | 9 | | | | | SP02876 | | 9 | | 150-199 |
| 507 | 20 | PA | | 9-0 | 33-21-11 | D11170 | | 10 | | | | | SP02878 | | 9 | | 150-199 |
| 508 | 20 | PA | | 6-0 | 33-21-11 | D11170 | | 7 | | | | | GD01940 | A.. | 2 | | 150-199 |
| 509 | 20 | PA | | 22-0 | 33-21-11 | SP02890 | | | 9 | | | | SP02862 | | 9 | | 150-199, 275-278 |
| 510 | 20 | PA | | 22-0 | 33-21-11 | SP02888 | | | 9 | | | | SP02864 | | 9 | | 150-199, 275-278 |
| 511 | 20 | PA | | 7-0 | 33-21-11 | SP02866 | | | S | | | | GD04874 | S.. | 2 | | 150-199, 275-278 |
| 512 | 20 | PA | | 21-0 | 33-21-11 | L00766 | | = G | E | | | | GD01940 | S.. | 2 | | 150-199 |
| 512 | 20 | PA | | 10-0 | 33-21-11 | SP01998 | | | 9 | | | | GD00960 | S.. | 2 | | 275-277 |
| 512 | 20 | PA | | 10-0 | 33-21-11 | L00762 | | = G | E | | | | GD00960 | S.. | 2 | | 278 |
| 679 | 22 | PA | | 22-0 | SPARE | D07096J | | | 13 | | | | D05912P | | 9 | | 280-299 |
| 680 | 20 | PA | | 18-0 | SPARE | D07096J | | | 14 | | | | GD01918 | S.. | 2 | | 280-299 |
| 681 | 20 | PA | | 18-0 | SPARE | D07096J | | | 16 | | | | GD01918 | A.. | 2 | | 280-299 |
| 682 | 22 | PA | | 22-0 | SPARE | D07096J | | | 15 | | | | D05912P | | 1 | | 280-299 |
| 683 | 22 | PA | | 22-0 | SPARE | D07096J | | | 17 | | | | D05912P | | 2 | | 280-299 |
| 686 | 20 | PA | | 18-0 | 33-21-11 | D07096J | | | 2 | | | | GD01918 | A.. | 2 | | 280-299 |
| 687 | 20 | PA | | 18-0 | 33-21-11 | D07096J | | | 3 | | | | GD01918 | S.. | 2 | | 280-299 |
| 688 | 20 | PA | | 18-0 | 33-21-11 | D07096J | | | 5 | | | | GD01918 | S.. | 2 | | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W0820
Page 12
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | |
| 689 | 20 | | PA | 18-0 | 33-21-11 | D07096J | | 4 | | | | GD01918 | A.. | 2 | | 280-299 |
| 690 | 20 | | PA | 18-0 | 33-21-11 | D07096J | | 10 | | | | GD01918 | S.. | 2 | | 280-299 |
| 691 | 20 | | PA | 18-0 | 33-21-11 | D07096J | | 11 | | | | GD01918 | A.. | 2 | | 280-299 |
| 692 | 20 | | PA | 18-0 | 33-21-11 | D07096J | | 7 | | | | GD01918 | A.. | 2 | | 280-299 |
| 693 | 20 | | PA | 18-0 | 33-21-11 | D07096J | | 8 | | | | GD01918 | S.. | 2 | | 280-299 |
| 807 | 20 | | PA | 21-0 | 33-21-11 | D05912P | | 5 | | | | SM00002 | | 9 | | 050-099 |
| A-E | | | | 0-0 | 33-21-11 | L00767 | | | BLK | | | SP02848 | | 9 | | 150-199 |
| A-F | | | | 0-0 | 33-21-11 | L00767 | | | BLK | | | SP02850 | | 9 | | 150-199 |
| A-G | | | | 0-0 | 33-21-11 | L00767 | | | WHT | | | SP02880 | | 9 | | 150-199 |
| A-H | | | | 0-0 | 33-21-11 | L00767 | | | WHT | | | SP02882 | | 9 | | 150-199 |
| A-I | | | | 0-0 | 33-21-11 | L00763 | | | RED | | | SP04052 | | 9 | | 275-277 |
| A-J | | | | 0-0 | 33-21-11 | L00763 | | | BLK | | | SP02852 | | 9 | | 150-199, 275-278 |
| A-K | | | | 0-0 | 33-21-11 | L00763 | | | BLK | | | SP02854 | | 9 | | 150-199, 275-278 |
| A-L | | | | 0-0 | 33-21-11 | L00763 | | | WHT | | | SP02884 | | 9 | | 150-199, 275-278 |
| A-M | | | | 0-0 | 33-21-11 | L00763 | | | WHT | | | SP02886 | | 9 | | 150-199, 275-278 |
| A-N | | | | 0-0 | 33-21-11 | L00759 | | | BLK | | | SP02858 | | 9 | | 150-199, 275-278 |
| A-P | | | | 0-0 | 33-21-11 | L00759 | | | BLK | | | SP02860 | | 9 | | 150-199, 275-278 |
| A-R | | | | 0-0 | 33-21-11 | L00759 | | | WHT | | | SP02888 | | 9 | | 150-199, 275-278 |
| A-S | | | | 0-0 | 33-21-11 | L00759 | | | WHT | | | SP02890 | | 9 | | 150-199, 275-278 |
| A-T | | | | 0-0 | 33-21-11 | L00759 | | | RED | | | SP02856 | | S | | 150-199, 275-278 |
| A-U | | | | 0-0 | 33-21-11 | L00758 | | | BLK | | | SP02868 | | 9 | | 150-199, 275-278 |
| A-V | | | | 0-0 | 33-21-11 | L00758 | | | BLK | | | SP02870 | | 9 | | 150-199, 275-278 |
| A-W | | | | 0-0 | 33-21-11 | L00758 | | | WHT | | | SP02864 | | 9 | | 150-199, 275-278 |
| A-X | | | | 0-0 | 33-21-11 | L00758 | | | WHT | | | SP02862 | | 9 | | 150-199, 275-278 |
| A-Y | | | | 0-0 | 33-21-11 | L00758 | | | RED | | | SP02866 | | S | | 150-199, 275-278 |
| B-E | | | | 0-0 | 33-21-11 | L00762 | | | BLK | | | SP02872 | | 9 | | 150-199, 275-278 |
| B-F | | | | 0-0 | 33-21-11 | L00762 | | | BLK | | | SP02874 | | 9 | | 150-199, 275-278 |
| B-G | | | | 0-0 | 33-21-11 | L00762 | | | WHT | | | SP02892 | | 9 | | 150-199, 275-278 |
| B-H | | | | 0-0 | 33-21-11 | L00762 | | | WHT | | | SP02894 | | 9 | | 150-199, 275-278 |
| B-J | | | | 0-0 | 33-21-11 | L00766 | | | BLK | | | SP02876 | | 9 | | 150-199 |
| B-K | | | | 0-0 | 33-21-11 | L00766 | | | BLK | | | SP02878 | | 9 | | 150-199 |
| B-L | | | | 0-0 | 33-21-11 | L00766 | | | WHT | | | SP02896 | | 9 | | 150-199 |
| B-M | | | | 0-0 | 33-21-11 | L00766 | | | WHT | | | SP02898 | | 9 | | 150-199 |
| F-A | | | | 0-0 | 33-21-11 | L00240 | | | BLK | | | SP00828 | | 9 | | ALL |
| F-B | | | | 0-0 | 33-21-11 | L00240 | | | BLK | | | SP00830 | | 9 | | ALL |
| F-C | | | | 0-0 | 33-21-11 | L00240 | | | WHT | | | SP00832 | | 9 | | ALL |
| F-D | | | | 0-0 | 33-21-11 | L00240 | | | WHT | | | SP00834 | | 9 | | ALL |
| F-E | | | | 0-0 | 33-21-11 | L00240 | | | RED | | | SP01990 | | S | | ALL |
| G-A | | | | 0-0 | 33-21-11 | L00242 | | | BLK | | | SP00824 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | |
| G-B | | | | | 0-0 | 33-21-11 | L00242 | | BLK | | | SP00826 | | 9 | | ALL |
| G-C | | | | | 0-0 | 33-21-11 | L00242 | | WHT | | | SP00820 | | 9 | | ALL |
| G-D | | | | | 0-0 | 33-21-11 | L00242 | | WHT | | | SP00822 | | 9 | | ALL |
| G-E | | | | | 0-0 | 33-21-11 | L00242 | | RED | | | SP01992 | | S | | ALL |
| H-A | | | | | 0-0 | 33-21-11 | L00241 | | BLK | | | SP00844 | | 9 | | 050-099 |
| H-A | | | | | 0-0 | 33-21-13 | L00241 | | BLK | | | SP00844 | | 9 | | 150-199, 275-278 |
| H-B | | | | | 0-0 | 33-21-11 | L00241 | | BLK | | | SP00846 | | 9 | | 050-099 |
| H-B | | | | | 0-0 | 33-21-13 | L00241 | | BLK | | | SP00846 | | 9 | | 150-199, 275-278 |
| H-C | | | | | 0-0 | 33-21-11 | L00241 | | WHT | | | SP00848 | | 9 | | 050-099 |
| H-C | | | | | 0-0 | 33-21-13 | L00241 | | WHT | | | SP00848 | | 9 | | 150-199, 275-278 |
| H-D | | | | | 0-0 | 33-21-11 | L00241 | | WHT | | | SP00850 | | 9 | | 050-099 |
| H-D | | | | | 0-0 | 33-21-13 | L00241 | | WHT | | | SP00850 | | 9 | | 150-199, 275-278 |
| H-E | | | | | 0-0 | 33-21-11 | L00241 | | RED | | | SP01994 | | S | | 050-099 |
| H-E | | | | | 0-0 | 33-21-13 | L00241 | | RED | | | SP01994 | | S | | 150-199, 275-278 |
| J-A | | | | | 0-0 | 33-21-11 | L00243 | | BLK | | | SP00840 | | 9 | | 050-099 |
| J-A | | | | | 0-0 | 33-21-13 | L00243 | | BLK | | | SP00840 | | 9 | | 150-199, 275-278 |
| J-B | | | | | 0-0 | 33-21-11 | L00243 | | BLK | | | SP00842 | | 9 | | 050-099 |
| J-B | | | | | 0-0 | 33-21-13 | L00243 | | BLK | | | SP00842 | | 9 | | 150-199, 275-278 |
| J-C | | | | | 0-0 | 33-21-11 | L00243 | | WHT | | | SP00836 | | 9 | | 050-099 |
| J-C | | | | | 0-0 | 33-21-13 | L00243 | | WHT | | | SP00836 | | 9 | | 150-199, 275-278 |
| J-D | | | | | 0-0 | 33-21-11 | L00243 | | WHT | | | SP00838 | | 9 | | 050-099 |
| J-D | | | | | 0-0 | 33-21-13 | L00243 | | WHT | | | SP00838 | | 9 | | 150-199, 275-278 |
| J-E | | | | | 0-0 | 33-21-11 | L00243 | | RED | | | SP01996 | | S | | 050-099 |
| J-E | | | | | 0-0 | 33-21-13 | L00243 | | RED | | | SP01996 | | S | | 150-199, 275-278 |
| K-A | | | | | 0-0 | 33-21-11 | L00232 | | BLK | | | SP00898 | | 9 | | 275-299 |
| K-B | | | | | 0-0 | 33-21-11 | L00232 | | BLK | | | SP00900 | | 9 | | 275-299 |
| K-C | | | | | 0-0 | 33-21-11 | L00232 | | WHT | | | SP00902 | | 9 | | 275-299 |
| K-D | | | | | 0-0 | 33-21-11 | L00232 | | WHT | | | SP00904 | | 9 | | 275-299 |
| K-E | | | | | 0-0 | 33-21-11 | L00762 | | RED | | | SP01998 | | 9 | | 275-277 |
| M-A | | | | | 0-0 | 33-21-11 | L00234 | | BLK | | | SP00914 | | 9 | | ALL |
| M-B | | | | | 0-0 | 33-21-11 | L00234 | | BLK | | | SP00916 | | 9 | | ALL |
| M-C | | | | | 0-0 | 33-21-11 | L00234 | | WHT | | | SP00918 | | 9 | | ALL |
| M-D | | | | | 0-0 | 33-21-11 | L00234 | | WHT | | | SP00920 | | 9 | | ALL |
| M-E | | | | | 0-0 | 33-21-11 | L00234 | | RED | | | SP02000 | | S | | ALL |
| N-A | | | | | 0-0 | 33-21-11 | L00235 | | BLK | | | SP00910 | | 9 | | ALL |
| N-B | | | | | 0-0 | 33-21-11 | L00235 | | BLK | | | SP00912 | | 9 | | ALL |
| N-C | | | | | 0-0 | 33-21-11 | L00235 | | WHT | | | SP00906 | | 9 | | ALL |
| N-D | | | | | 0-0 | 33-21-11 | L00235 | | WHT | | | SP00908 | | 9 | | ALL |
| N-E | | | | | 0-0 | 33-21-11 | L00235 | | RED | | | SP02002 | | S | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 14

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | |
| P-A | | | | 0-0 | 33-21-13 | L00262 | | BLK | | | SP01386 | | 9 | | ALL |
| P-B | | | | 0-0 | 33-21-13 | L00262 | | BLK | | | SP01388 | | 9 | | ALL |
| P-C | | | | 0-0 | 33-21-13 | L00262 | | WHT | | | SP01390 | | 9 | | ALL |
| P-D | | | | 0-0 | 33-21-13 | L00262 | | WHT | | | SP01392 | | 9 | | ALL |
| P-E | | | | 0-0 | 33-21-13 | L00262 | | RED | | | SP02004 | | S | | ALL |
| R-A | | | | 0-0 | 33-21-13 | L00263 | | BLK | | | SP01394 | | 9 | | ALL |
| R-B | | | | 0-0 | 33-21-13 | L00263 | | BLK | | | SP01396 | | 9 | | ALL |
| R-C | | | | 0-0 | 33-21-13 | L00263 | | WHT | | | SP01398 | | 9 | | ALL |
| R-D | | | | 0-0 | 33-21-13 | L00263 | | WHT | | | SP01400 | | 9 | | ALL |
| R-E | | | | 0-0 | 33-21-13 | L00263 | | RED | | | SP02006 | | S | | ALL |
| S-A | | | | 0-0 | 33-21-13 | L00264 | | BLK | | | SP01402 | | 9 | | ALL |
| S-B | | | | 0-0 | 33-21-13 | L00264 | | BLK | | | SP01404 | | 9 | | ALL |
| S-C | | | | 0-0 | 33-21-13 | L00264 | | WHT | | | SP01406 | | 9 | | ALL |
| S-D | | | | 0-0 | 33-21-13 | L00264 | | WHT | | | SP01408 | | 9 | | ALL |
| S-E | | | | 0-0 | 33-21-13 | L00264 | | RED | | | SP02008 | | S | | ALL |
| T-A | | | | 0-0 | 33-21-13 | L00265 | | BLK | | | SP01410 | | 9 | | ALL |
| T-B | | | | 0-0 | 33-21-13 | L00265 | | BLK | | | SP01412 | | 9 | | ALL |
| T-C | | | | 0-0 | 33-21-13 | L00265 | | WHT | | | SP01414 | | 9 | | ALL |
| T-D | | | | 0-0 | 33-21-13 | L00265 | | WHT | | | SP01416 | | 9 | | ALL |
| T-E | | | | 0-0 | 33-21-13 | L00265 | | RED | | | SP02010 | | S | | ALL |
| U-A | | | | 0-0 | 33-21-13 | L00266 | | BLK | | | SP01418 | | 9 | | ALL |
| U-B | | | | 0-0 | 33-21-13 | L00266 | | BLK | | | SP01420 | | 9 | | ALL |
| U-C | | | | 0-0 | 33-21-13 | L00266 | | WHT | | | SP01422 | | 9 | | ALL |
| U-D | | | | 0-0 | 33-21-13 | L00266 | | WHT | | | SP01424 | | 9 | | ALL |
| U-E | | | | 0-0 | 33-21-13 | L00266 | | RED | | | SP02012 | | S | | ALL |
| V-A | | | | 0-0 | 33-21-13 | L00267 | | BLK | | | SP01426 | | 9 | | ALL |
| V-B | | | | 0-0 | 33-21-13 | L00267 | | BLK | | | SP01428 | | 9 | | ALL |
| V-C | | | | 0-0 | 33-21-13 | L00267 | | WHT | | | SP01430 | | 9 | | ALL |
| V-D | | | | 0-0 | 33-21-13 | L00267 | | WHT | | | SP01432 | | 9 | | ALL |
| V-E | | | | 0-0 | 33-21-13 | L00267 | | RED | | | SP02014 | | S | | ALL |
| W-A | | | | 0-0 | 33-21-13 | L00284 | | BLK | | | SP01434 | | 9 | | 050-099 |
| W-B | | | | 0-0 | 33-21-13 | L00284 | | BLK | | | SP01436 | | 9 | | 050-099 |
| W-C | | | | 0-0 | 33-21-13 | L00284 | | WHT | | | SP01438 | | 9 | | 050-099 |
| W-D | | | | 0-0 | 33-21-13 | L00284 | | WHT | | | SP01440 | | 9 | | 050-099 |
| W-E | | | | 0-0 | 33-21-13 | L00284 | | RED | | | SP02016 | | S | | 050-099 |
| X-A | | | | 0-0 | 33-21-13 | L00285 | | BLK | | | SP01442 | | 9 | | 050-099 |
| X-B | | | | 0-0 | 33-21-13 | L00285 | | BLK | | | SP01444 | | 9 | | 050-099 |
| X-C | | | | 0-0 | 33-21-13 | L00285 | | WHT | | | SP01446 | | 9 | | 050-099 |
| X-D | | | | 0-0 | 33-21-13 | L00285 | | WHT | | | SP01448 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0822 | 286T0822 | | | CENTER MID DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | |
| X-E | | | | | 0-0 | 33-21-13 | L00285 | | RED | | SP02018 | | S | | 050-099 |
| W0824 | 286T0824 | | | CENTER AFT DIRECT,INDIRECT,GALLEY LIGHTING | | | | | | | | | | | |
| 001 | 22 | | PA | | 16-10 | 33-21-14 | D00370 | | 2 | | SP00922 | | 9 | | 050-099 |
| 001 | 20 | | PA | | 19-11 | 33-21-14 | D00370 | | 2 | | SP00922 | | 9 | | 150-199, 275-299 |
| 002 | 22 | | PA | | 16-10 | 33-21-14 | D00370 | | 3 | | SP00924 | | 9 | | 050-099 |
| 002 | 20 | | PA | | 19-11 | 33-21-14 | D00370 | | 3 | | SP00924 | | 9 | | 150-199, 275-299 |
| 003 | 20 | | PA | | 8-9 | 33-21-14 | D00370 | | 5 | | SM00001 | | 9 | | 050-099 |
| 003 | 20 | | PA | | 7-9 | 33-21-14 | D00370 | | 5 | | SM00001 | | 9 | | 150-199, 275-299 |
| 004 | 20 | | PA | | 3-11 | 33-21-14 | D00370 | | 7 | | GD01758 | A.. | 2 | | 050-099 |
| 004 | 20 | | PA | | 4-5 | 33-21-14 | D00370 | | 7 | | GD01758 | A.. | 2 | | 150-199, 275-299 |
| 005 | 20 | | PA | | 3-11 | 33-21-14 | D00370 | | 8 | | GD01758 | S.. | 2 | | 050-099 |
| 005 | 20 | | PA | | 4-5 | 33-21-14 | D00370 | | 8 | | GD01758 | S.. | 2 | | 150-199, 275-299 |
| 006 | 22 | | PA | | 13-1 | 33-21-14 | D00370 | | 9 | | SP00930 | | 9 | | 050-099 |
| 006 | 20 | | PA | | 4-9 | 33-21-14 | D00370 | | 9 | | SP00930 | | 9 | | 150-199, 275-299 |
| 007 | 22 | | PA | | 13-1 | 33-21-14 | D00370 | | 10 | | SP00932 | | 9 | | 050-099 |
| 007 | 20 | | PA | | 4-9 | 33-21-14 | D00370 | | 10 | | SP00932 | | 9 | | 150-199, 275-299 |
| 008 | 22 | | PA | | 13-1 | 33-21-14 | D00370 | | 11 | | SP00934 | | 9 | | 050-099 |
| 008 | 20 | | PA | | 4-9 | 33-21-14 | D00370 | | 11 | | SP00934 | | 9 | | 150-199, 275-299 |
| 009 | 22 | | PA | | 13-1 | 33-21-14 | D00370 | | 12 | | SP00936 | | 9 | | 050-099 |
| 009 | 20 | | PA | | 4-9 | 33-21-14 | D00370 | | 12 | | SP00936 | | 9 | | 150-199, 275-299 |
| 010 | 20 | | PA | | 9-10 | 33-21-14 | SP02020 | | | S | GD01756 | S.. | 2 | | 050-099 |
| 010 | 20 | | PA | | 5-4 | 33-21-14 | SP02020 | | | S | GD01758 | S.. | 2 | | 150-199, 275-299 |
| 011 | 20 | | PA | | 11-3 | 33-21-14 | SP02022 | | | S | GD01750 | S.. | 2 | | 050-099 |
| 011 | 20 | | PA | | 11-6 | 33-21-14 | SP02022 | | | S | GD01906 | S.. | 2 | | 150-199, 275-299 |
| 012 | 22 | | PA | | 26-0 | 33-21-14 | SP00926 | | 9 | | SP00934 | | 9 | | 050-099 |
| 012 | 20 | | PA | | 22-0 | 33-21-14 | SP00926 | | 9 | | SP00934 | | 9 | | 150-199, 275-299 |
| 013 | 22 | | PA | | 26-0 | 33-21-14 | SP00928 | | 9 | | SP00936 | | 9 | | 050-099 |
| 013 | 20 | | PA | | 22-0 | 33-21-14 | SP00928 | | 9 | | SP00936 | | 9 | | 150-199, 275-299 |
| 014 | 22 | | PA | | 21-4 | 33-21-14 | D00420 | | 2 | | SP00938 | | 9 | | 050-099 |
| 014 | 20 | | PA | | 24-0 | 33-21-14 | D00420 | | 2 | | SP00938 | | 9 | | 150-199, 275-299 |
| 015 | 22 | | PA | | 21-4 | 33-21-14 | D00420 | | 3 | | SP00940 | | 9 | | 050-099 |
| 015 | 20 | | PA | | 24-0 | 33-21-14 | D00420 | | 3 | | SP00940 | | 9 | | 150-199, 275-299 |
| 016 | 20 | | PA | | 17-9 | 33-21-14 | D00420 | | 5 | | SM00001 | | 9 | | 050-099 |
| 016 | 20 | | PA | | 28-9 | 33-21-14 | D00420 | | 5 | | SM00001 | | 9 | | 150-199, 275-299 |
| 017 | 20 | | PA | | 5-0 | 33-21-14 | D00420 | | 7 | | GD01760 | A.. | 2 | | 050-099 |
| 017 | 20 | | PA | | 5-4 | 33-21-14 | D00420 | | 7 | | GD01760 | A.. | 2 | | 150-199, 275-299 |
| 018 | 20 | | PA | | 5-0 | 33-21-14 | D00420 | | 8 | | GD01760 | S.. | 2 | | 050-099 |
| 018 | 20 | | PA | | 5-4 | 33-21-14 | D00420 | | 8 | | GD01760 | S.. | 2 | | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0820
Page 16
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0824 | 286T0824 | | | CENTER AFT DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | | |
| 019 | 22 | | PA | 13-4 | 33-21-14 | D00420 | | 9 | | | | | SP00946 | | 9 | | 050-099 |
| 019 | 20 | | PA | 13-5 | 33-21-14 | D00420 | | 9 | | | | | SP00946 | | 9 | | 150-199, 275-299 |
| 020 | 22 | | PA | 13-4 | 33-21-14 | D00420 | | 10 | | | | | SP00948 | | 9 | | 050-099 |
| 020 | 20 | | PA | 13-5 | 33-21-14 | D00420 | | 10 | | | | | SP00948 | | 9 | | 150-199, 275-299 |
| 021 | 22 | | PA | 13-4 | 33-21-14 | D00420 | | 11 | | | | | SP00950 | | 9 | | 050-099 |
| 021 | 20 | | PA | 13-5 | 33-21-14 | D00420 | | 11 | | | | | SP00950 | | 9 | | 150-199, 275-299 |
| 022 | 22 | | PA | 13-4 | 33-21-14 | D00420 | | 12 | | | | | SP00952 | | 9 | | 050-099 |
| 022 | 20 | | PA | 13-5 | 33-21-14 | D00420 | | 12 | | | | | SP00952 | | 9 | | 150-199, 275-299 |
| 023 | 20 | | PA | 12-9 | 33-21-14 | SP02024 | | | S | | | | GD01760 | S.. | 2 | | 050-099 |
| 023 | 20 | | PA | 13-3 | 33-21-14 | SP02024 | | | S | | | | GD01760 | S.. | 2 | | 150-199, 275-299 |
| 024 | 20 | | PA | 14-3 | 33-21-14 | SP02026 | | | S | | | | GD01756 | S.. | 2 | | 050-099 |
| 024 | 20 | | PA | 16-10 | 33-21-14 | SP02026 | | | S | | | | GD04904 | S.. | 2 | | 150-199, 275-299 |
| 025 | 22 | | PA | 31-4 | 33-21-14 | SP00942 | | 9 | | | | | SP00950 | | 9 | | 050-099 |
| 025 | 20 | | PA | 34-1 | 33-21-14 | SP00942 | | 9 | | | | | SP00950 | | 9 | | 150-199, 275-299 |
| 026 | 22 | | PA | 31-4 | 33-21-14 | SP00944 | | 9 | | | | | SP00952 | | 9 | | 050-099 |
| 026 | 20 | | PA | 34-1 | 33-21-14 | SP00944 | | 9 | | | | | SP00952 | | 9 | | 150-199, 275-299 |
| 027 | 20 | | PA | 6-0 | 33-21-14 | D05916P | | 1 | | | | | SM00001 | | 9 | | 050-099 |
| 027 | 20 | | PA | 5-4 | 33-21-14 | D05916P | | 1 | | | | | SM00001 | | 9 | | 150-199, 275-299 |
| 028 | 22 | | PA | 14-8 | 33-21-14 | D00380 | | 2 | | | | | SP01034 | | 9 | | 050-099 |
| 028 | 20 | | PA | 14-5 | 33-21-14 | D00380 | | 2 | | | | | SP01034 | | 9 | | 150-152, 275-299 |
| 028 | 20 | | PA | 20-6 | 33-21-14 | D00380 | | 2 | | | | | SP01034 | | 9 | | 153-199 |
| 029 | 22 | | PA | 14-8 | 33-21-14 | D00380 | | 3 | | | | | SP01036 | | 9 | | 050-099 |
| 029 | 20 | | PA | 14-5 | 33-21-14 | D00380 | | 3 | | | | | SP01036 | | 9 | | 150-152, 275-299 |
| 029 | 20 | | PA | 20-6 | 33-21-14 | D00380 | | 3 | | | | | SP01036 | | 9 | | 153-199 |
| 030 | 20 | | PA | 2-11 | 33-21-14 | D00380 | | 5 | | | | | SM00002 | | 9 | | 050-099 |
| 030 | 20 | | PA | 2-9 | 33-21-14 | D00380 | | 5 | | | | | SM00002 | | 9 | | 150-152 |
| 030 | 20 | | PA | 10-4 | 33-21-14 | D00380 | | 5 | | | | | SM00002 | | 9 | | 153-199 |
| 030 | 20 | | PA | 35-2 | 33-21-14 | D00380 | | 5 | | | | | D05916P | | 2 | | 275-299 |
| 031 | 20 | | PA | 3-7 | 33-21-14 | D00380 | | 7 | | | | | GD01760 | A.. | 2 | | 050-099 |
| 031 | 20 | | PA | 3-8 | 33-21-14 | D00380 | | 7 | | | | | GD01760 | A.. | 2 | | 150-152, 275-299 |
| 031 | 20 | | PA | 10-2 | 33-21-14 | D00380 | | 7 | | | | | GD01760 | A.. | 2 | | 153-199 |
| 032 | 20 | | PA | 3-7 | 33-21-14 | D00380 | | 8 | | | | | GD01760 | S.. | 2 | | 050-099 |
| 032 | 20 | | PA | 3-8 | 33-21-14 | D00380 | | 8 | | | | | GD01760 | S.. | 2 | | 150-152, 275-299 |
| 032 | 20 | | PA | 10-2 | 33-21-14 | D00380 | | 8 | | | | | GD01760 | S.. | 2 | | 153-199 |
| 033 | 22 | | PA | 18-7 | 33-21-14 | D00380 | | 9 | | | | | SP01042 | | 9 | | 050-099 |
| 033 | 20 | | PA | 18-7 | 33-21-14 | D00380 | | 9 | | | | | SP01042 | | 9 | | 150-152, 275-299 |
| 033 | 20 | | PA | 11-11 | 33-21-14 | D00380 | | 9 | | | | | SP01042 | | 9 | | 153-199 |
| 034 | 22 | | PA | 18-7 | 33-21-14 | D00380 | | 10 | | | | | SP01044 | | 9 | | 050-099 |
| 034 | 20 | | PA | 18-7 | 33-21-14 | D00380 | | 10 | | | | | SP01044 | | 9 | | 150-152, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 17

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0824 | 286T0824 | | | CENTER AFT DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | | | | |
| 034 | 20 | PA | | | 11-11 | 33-21-14 | D00380 | | 10 | | | | | | SP01044 | | 9 | | 153-199 |
| 035 | 22 | PA | | | 18-7 | 33-21-14 | D00380 | | 11 | | | | | | SP01046 | | 9 | | 050-099 |
| 035 | 20 | PA | | | 18-7 | 33-21-14 | D00380 | | 11 | | | | | | SP01046 | | 9 | | 150-152, 275-299 |
| 035 | 20 | PA | | | 11-11 | 33-21-14 | D00380 | | 11 | | | | | | SP01046 | | 9 | | 153-199 |
| 036 | 22 | PA | | | 18-7 | 33-21-14 | D00380 | | 12 | | | | | | SP01048 | | 9 | | 050-099 |
| 036 | 20 | PA | | | 18-7 | 33-21-14 | D00380 | | 12 | | | | | | SP01048 | | 9 | | 150-152, 275-299 |
| 036 | 20 | PA | | | 11-11 | 33-21-14 | D00380 | | 12 | | | | | | SP01048 | | 9 | | 153-199 |
| 037 | 20 | PA | | | 11-10 | 33-21-14 | SP02028 | | | S | | | | | GD01774 | S.. | 2 | | 050-099 |
| 037 | 20 | PA | | | 12-6 | 33-21-14 | SP02028 | | | S | | | | | GD01774 | S.. | 2 | | 150-199, 275-299 |
| 038 | 20 | PA | | | 12-1 | 33-21-14 | SP02030 | | | S | | | | | GD01760 | S.. | 2 | | 050-099 |
| 038 | 20 | PA | | | 11-10 | 33-21-14 | SP02030 | | | S | | | | | GD01760 | S.. | 2 | | 150-199, 275-299 |
| 039 | 22 | PA | | | 29-0 | 33-21-14 | SP01038 | | 9 | | | | | | SP01046 | | 9 | | 050-099 |
| 039 | 20 | PA | | | 28-10 | 33-21-14 | SP01038 | | 9 | | | | | | SP01046 | | 9 | | 150-199, 275-299 |
| 040 | 22 | PA | | | 29-0 | 33-21-14 | SP01040 | | 9 | | | | | | SP01048 | | 9 | | 050-099 |
| 040 | 20 | PA | | | 28-10 | 33-21-14 | SP01040 | | 9 | | | | | | SP01048 | | 9 | | 150-199, 275-299 |
| 041 | 22 | PA | | | 16-5 | 33-21-14 | D00388 | | 2 | | | | | | SP01050 | | 9 | | 050-099 |
| 041 | 20 | PA | | | 15-1 | 33-21-14 | D00388 | | 2 | | | | | | SP01050 | | 9 | | 150-199, 275-299 |
| 042 | 22 | PA | | | 16-5 | 33-21-14 | D00388 | | 3 | | | | | | SP01052 | | 9 | | 050-099 |
| 042 | 20 | PA | | | 15-1 | 33-21-14 | D00388 | | 3 | | | | | | SP01052 | | 9 | | 150-199, 275-299 |
| 043 | 20 | PA | | | 14-8 | 33-21-14 | D00388 | | 5 | | | | | | SM00002 | | 9 | | 050-099 |
| 043 | 20 | PA | | | 13-7 | 33-21-14 | D00388 | | 5 | | | | | | SM00002 | | 9 | | 150-199 |
| 043 | 20 | PA | | | 45-6 | 33-21-14 | D00388 | | 5 | | | | | | D05916P | 3 | | | 275-299 |
| 044 | 20 | PA | | | 3-11 | 33-21-14 | D00388 | | 7 | | | | | | GD01776 | A.. | 2 | | ALL |
| 045 | 20 | PA | | | 3-11 | 33-21-14 | D00388 | | 8 | | | | | | GD01776 | S.. | 2 | | ALL |
| 046 | 22 | PA | | | 9-0 | 33-21-14 | D00388 | | 9 | | | | | | SP01058 | | 9 | | 050-099 |
| 046 | 20 | PA | | | 9-10 | 33-21-14 | D00388 | | 9 | | | | | | SP01058 | | 9 | | 150-199, 275-299 |
| 047 | 22 | PA | | | 9-0 | 33-21-14 | D00388 | | 10 | | | | | | SP01060 | | 9 | | 050-099 |
| 047 | 20 | PA | | | 9-10 | 33-21-14 | D00388 | | 10 | | | | | | SP01060 | | 9 | | 150-199, 275-299 |
| 048 | 22 | PA | | | 9-0 | 33-21-14 | D00388 | | 11 | | | | | | SP01062 | | 9 | | 050-099 |
| 048 | 20 | PA | | | 9-10 | 33-21-14 | D00388 | | 11 | | | | | | SP01062 | | 9 | | 150-199, 275-299 |
| 049 | 22 | PA | | | 9-0 | 33-21-14 | D00388 | | 12 | | | | | | SP01064 | | 9 | | 050-099 |
| 049 | 20 | PA | | | 9-10 | 33-21-14 | D00388 | | 12 | | | | | | SP01064 | | 9 | | 150-199, 275-299 |
| 050 | 20 | PA | | | 8-9 | 33-21-14 | SP02032 | | | S | | | | | GD01776 | S.. | 2 | | 050-099 |
| 050 | 20 | PA | | | 9-5 | 33-21-14 | SP02032 | | | S | | | | | GD01776 | S.. | 2 | | 150-199 |
| 050 | 20 | PA | | | 9-5 | 33-21-14 | L00280 | | | = G | E | | | | GD01776 | S.. | 2 | | 275-299 |
| 051 | 20 | PA | | | 10-10 | 33-21-14 | SP02034 | | | S | | | | | GD01774 | S.. | 2 | | 050-099 |
| 051 | 20 | PA | | | 10-8 | 33-21-14 | SP02034 | | | S | | | | | GD01774 | S.. | 2 | | 150-199 |
| 051 | 20 | PA | | | 10-8 | 33-21-14 | L00281 | | | = G | E | | | | GD01774 | S.. | 2 | | 275-299 |
| 052 | 20 | PA | | | 21-6 | 33-21-14 | SP01054 | | 9 | | | | | | SP01062 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 18

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0824 | 286T0824 | | | CENTER AFT DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | | |
| 052 | 20 | PA | | 21-11 | 33-21-14 | SP01054 | | | | 9 | | | | SP01062 | | 9 | 150-199, 275-299 |
| 053 | 20 | PA | | 21-6 | 33-21-14 | SP01056 | | | | 9 | | | | SP01064 | | 9 | 050-099 |
| 053 | 20 | PA | | 21-11 | 33-21-14 | SP01056 | | | | 9 | | | | SP01064 | | 9 | 150-199, 275-299 |
| 054 | 20 | PA | | 22-2 | 33-21-14 | D05916P | | | 2 | | | | | SM00002 | | 9 | 050-099 |
| 054 | 20 | PA | | 32-11 | 33-21-14 | D05916P | | | 2 | | | | | SM00002 | | 9 | 150-199 |
| 055 | 22 | PA | | 10-5 | 33-21-14 | D00756 | | | 2 | | | | | SP01066 | | 9 | 050-099 |
| 055 | 20 | PA | | 18-8 | 33-21-14 | D00756 | | | 2 | | | | | SP01066 | | 9 | 150-199, 275-299 |
| 056 | 22 | PA | | 10-5 | 33-21-14 | D00756 | | | 3 | | | | | SP01068 | | 9 | 050-099 |
| 056 | 20 | PA | | 18-8 | 33-21-14 | D00756 | | | 3 | | | | | SP01068 | | 9 | 150-199, 275-299 |
| 057 | 22 | PA | | 13-8 | 33-21-14 | D00756 | | | 9 | | | | | SP01074 | | 9 | 050-099 |
| 057 | 20 | PA | | 10-0 | 33-21-14 | D00756 | | | 9 | | | | | SP01074 | | 9 | 150-199, 275-299 |
| 058 | 22 | PA | | 13-8 | 33-21-14 | D00756 | | | 10 | | | | | SP01076 | | 9 | 050-099 |
| 058 | 20 | PA | | 10-0 | 33-21-14 | D00756 | | | 10 | | | | | SP01076 | | 9 | 150-199, 275-299 |
| 059 | 22 | PA | | 13-8 | 33-21-14 | D00756 | | | 12 | | | | | SP01078 | | 9 | 050-099 |
| 059 | 20 | PA | | 10-0 | 33-21-14 | D00756 | | | 12 | | | | | SP01078 | | 9 | 150-199, 275-299 |
| 060 | 22 | PA | | 13-8 | 33-21-14 | D00756 | | | 11 | | | | | SP01080 | | 9 | 050-099 |
| 060 | 20 | PA | | 10-0 | 33-21-14 | D00756 | | | 11 | | | | | SP01080 | | 9 | 150-199, 275-299 |
| 061 | 20 | PA | | 19-1 | 33-21-14 | SP01070 | | | | 9 | | | | SP01078 | | 9 | 050-099 |
| 061 | 20 | PA | | 25-8 | 33-21-14 | SP01070 | | | | 9 | | | | SP01078 | | 9 | 150-199, 275-299 |
| 062 | 20 | PA | | 19-1 | 33-21-14 | SP01072 | | | | 9 | | | | SP01080 | | 9 | 050-099 |
| 062 | 20 | PA | | 25-8 | 33-21-14 | SP01072 | | | | 9 | | | | SP01080 | | 9 | 150-199, 275-299 |
| 063 | 20 | PA | | 6-4 | 33-21-14 | SP02038 | | | | S | | | | GD01750 | S.. | 2 | 050-099 |
| 063 | 20 | PA | | 6-7 | 33-21-14 | SP02038 | | | | S | | | | GD01906 | S.. | 2 | 150-199, 275-299 |
| 064 | 20 | PA | | 7-6 | 33-21-14 | SP02036 | | | | S | | | | GD01748 | S.. | 2 | 050-099 |
| 064 | 20 | PA | | 14-5 | 33-21-14 | SP02036 | | | | S | | | | GD01952 | S.. | 2 | 150-199, 275-299 |
| 065 | 20 | PA | | 4-6 | 33-21-14 | D00756 | | | 7 | | | | | GD01748 | A.. | 2 | 050-099 |
| 065 | 20 | PA | | 4-7 | 33-21-14 | D00756 | | | 7 | | | | | GD01748 | A.. | 2 | 150-199, 275-299 |
| 066 | 20 | PA | | 4-6 | 33-21-14 | D00756 | | | 8 | | | | | GD01748 | S.. | 2 | 050-099 |
| 066 | 20 | PA | | 4-7 | 33-21-14 | D00756 | | | 8 | | | | | GD01748 | S.. | 2 | 150-199, 275-299 |
| 067 | 20 | PA | | 7-5 | 33-21-14 | D00756 | | | 5 | | | | | SM00001 | | 9 | ALL |
| 081 | 20 | PA | | 14-5 | 33-21-14 | D11214 | | | 2 | | | | | SP02916 | | 9 | 150-199, 275-299 |
| 082 | 20 | PA | | 14-5 | 33-21-14 | D11214 | | | 3 | | | | | SP02918 | | 9 | 150-199, 275-299 |
| 083 | 20 | PA | | 4-9 | 33-21-14 | D11214 | | | 9 | | | | | SP02920 | | 9 | 150-199, 275-299 |
| 084 | 20 | PA | | 4-9 | 33-21-14 | D11214 | | | 10 | | | | | SP02922 | | 9 | 150-199, 275-299 |
| 085 | 20 | PA | | 4-9 | 33-21-14 | D11214 | | | 12 | | | | | SP02924 | | 9 | 150-199, 275-299 |
| 086 | 20 | PA | | 4-9 | 33-21-14 | D11214 | | | 11 | | | | | SP02926 | | 9 | 150-199, 275-299 |
| 087 | 20 | PA | | 4-1 | 33-21-14 | D11214 | | | 7 | | | | | GD04906 | A.. | 2 | 150-199, 275-299 |
| 088 | 20 | PA | | 4-1 | 33-21-14 | D11214 | | | 8 | | | | | GD04906 | S.. | 2 | 150-199, 275-299 |
| 089 | 20 | PA | | 22-6 | 33-21-14 | D11218 | | | 5 | | | | | SM00003 | | 9 | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 19

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0824 | 286T0824 | | | CENTER AFT DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | |
| 089 | 20 | | PA | | 18-8 | 33-21-14 | D11218 | | | | SM00003 | | | | 275-299 |
| 090 | 20 | | PA | | 5-5 | 33-21-14 | D11218 | | | | SP02944 | | | | 150-199 |
| 090 | 20 | | PA | | 9-8 | 33-21-14 | D11218 | | | | SP02944 | | | | 275-299 |
| 091 | 20 | | PA | | 5-5 | 33-21-14 | D11218 | | | | SP02946 | | | | 150-199 |
| 091 | 20 | | PA | | 9-8 | 33-21-14 | D11218 | | | | SP02946 | | | | 275-299 |
| 092 | 20 | | PA | | 20-9 | 33-21-14 | D11218 | | | | SP02930 | | | | 150-199 |
| 092 | 20 | | PA | | 16-11 | 33-21-14 | D11218 | | | | SP02930 | | | | 275-299 |
| 093 | 20 | | PA | | 20-9 | 33-21-14 | D11218 | | | | SP02932 | | | | 150-199 |
| 093 | 20 | | PA | | 16-11 | 33-21-14 | D11218 | | | | SP02932 | | | | 275-299 |
| 094 | 20 | | PA | | 6-3 | 33-21-14 | D11218 | | | | GD04908 | A.. | | | 150-199 |
| 094 | 20 | | PA | | 3-9 | 33-21-14 | D11218 | | | | GD04908 | A.. | | | 275-299 |
| 095 | 20 | | PA | | 5-5 | 33-21-14 | D11218 | | | | SP02940 | | | | 150-199 |
| 095 | 20 | | PA | | 9-8 | 33-21-14 | D11218 | | | | SP02940 | | | | 275-299 |
| 096 | 20 | | PA | | 5-5 | 33-21-14 | D11218 | | | | SP02942 | | | | 150-199 |
| 096 | 20 | | PA | | 9-8 | 33-21-14 | D11218 | | | | SP02942 | | | | 275-299 |
| 097 | 20 | | PA | | 6-3 | 33-21-14 | D11218 | | | | GD04908 | S.. | | | 150-199 |
| 097 | 20 | | PA | | 3-9 | 33-21-14 | D11218 | | | | GD04908 | S.. | | | 275-299 |
| 098 | 20 | | PA | | 5-4 | 33-21-14 | D05916P | | | | SM00003 | | | | 150-199, 275-299 |
| 099 | 20 | | PA | | 14-10 | 33-21-14 | D11214 | | | | SM00003 | | | | 150-199, 275-299 |
| 100 | 20 | | PA | | 8-8 | 33-21-14 | SP02910 | | | S | GD01758 | S.. | | | 150-199, 275-299 |
| 101 | 20 | | PA | | 16-8 | 33-21-14 | SP02912 | | | 9 | SP02926 | | | | 150-199, 275-299 |
| 102 | 20 | | PA | | 16-8 | 33-21-14 | SP02914 | | | 9 | SP02924 | | | | 150-199, 275-299 |
| 103 | 20 | | PA | | 4-10 | 33-21-14 | SP02928 | | | S | GD04906 | S.. | | | 150-199, 275-299 |
| 104 | 20 | | PA | | 14-4 | 33-21-14 | SP02938 | | | S | GD04906 | S.. | | | 150-199, 275-299 |
| 105 | 20 | | PA | | 13-1 | 33-21-14 | SP02948 | | | S | GD04906 | S.. | | | 150-199, 275-299 |
| 106 | 20 | | PA | | 23-9 | 33-21-14 | SP02936 | | | 9 | SP02940 | | | | 150-199, 275-299 |
| 107 | 20 | | PA | | 23-9 | 33-21-14 | SP02934 | | | 9 | SP02942 | | | | 150-199, 275-299 |
| A-A | | | | | 0-0 | 33-21-14 | L00270 | | | BLK | SP00930 | | | | ALL |
| A-B | | | | | 0-0 | 33-21-14 | L00270 | | | BLK | SP00932 | | | | ALL |
| A-C | | | | | 0-0 | 33-21-14 | L00270 | | | WHT | SP00934 | | | | ALL |
| A-D | | | | | 0-0 | 33-21-14 | L00270 | | | WHT | SP00936 | | | | ALL |
| A-E | | | | | 0-0 | 33-21-14 | L00270 | | | RED | SP02020 | | | | ALL |
| A-F | | | | | 0-0 | 33-21-14 | L00771 | | | BLK | SP02916 | | | | 150-199, 275-299 |
| A-G | | | | | 0-0 | 33-21-14 | L00771 | | | BLK | SP02918 | | | | 150-199, 275-299 |
| A-H | | | | | 0-0 | 33-21-14 | L00771 | | | WHT | SP02912 | | | | 150-199, 275-299 |
| A-J | | | | | 0-0 | 33-21-14 | L00771 | | | WHT | SP02914 | | | | 150-199, 275-299 |
| A-K | | | | | 0-0 | 33-21-14 | L00771 | | | RED | SP02910 | | | | 150-199, 275-299 |
| A-L | | | | | 0-0 | 33-21-14 | L00770 | | | BLK | SP02920 | | | | 150-199, 275-299 |
| A-M | | | | | 0-0 | 33-21-14 | L00770 | | | BLK | SP02922 | | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 20

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0824 | 286T0824 | | | CENTER AFT DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | | | | |
| A-N | | | | 0-0 | 33-21-14 | L00770 | | WHT | | | | | | SP02926 | | 9 | | 150-199, 275-299 |
| A-P | | | | 0-0 | 33-21-14 | L00770 | | WHT | | | | | | SP02924 | | 9 | | 150-199, 275-299 |
| A-R | | | | 0-0 | 33-21-14 | L00770 | | RED | | | | | | SP02928 | | S | | 150-199, 275-299 |
| A-S | | | | 0-0 | 33-21-14 | L00775 | | BLK | | | | | | SP02930 | | 9 | | 150-199, 275-299 |
| A-T | | | | 0-0 | 33-21-14 | L00775 | | BLK | | | | | | SP02932 | | 9 | | 150-199, 275-299 |
| A-U | | | | 0-0 | 33-21-14 | L00775 | | WHT | | | | | | SP02934 | | 9 | | 150-199, 275-299 |
| A-V | | | | 0-0 | 33-21-14 | L00775 | | WHT | | | | | | SP02936 | | 9 | | 150-199, 275-299 |
| A-W | | | | 0-0 | 33-21-14 | L00775 | | RED | | | | | | SP02938 | | S | | 150-199, 275-299 |
| B-A | | | | 0-0 | 33-21-14 | L00271 | | BLK | | | | | | SP00922 | | 9 | | ALL |
| B-B | | | | 0-0 | 33-21-14 | L00271 | | BLK | | | | | | SP00924 | | 9 | | ALL |
| B-C | | | | 0-0 | 33-21-14 | L00271 | | WHT | | | | | | SP00926 | | 9 | | ALL |
| B-D | | | | 0-0 | 33-21-14 | L00271 | | WHT | | | | | | SP00928 | | 9 | | ALL |
| B-E | | | | 0-0 | 33-21-14 | L00271 | | RED | | | | | | SP02022 | | S | | ALL |
| B-F | | | | 0-0 | 33-21-14 | L00774 | | BLK | | | | | | SP02944 | | 9 | | 150-199, 275-299 |
| B-G | | | | 0-0 | 33-21-14 | L00774 | | BLK | | | | | | SP02946 | | 9 | | 150-199, 275-299 |
| B-H | | | | 0-0 | 33-21-14 | L00774 | | WHT | | | | | | SP02942 | | 9 | | 150-199, 275-299 |
| B-J | | | | 0-0 | 33-21-14 | L00774 | | WHT | | | | | | SP02940 | | 9 | | 150-199, 275-299 |
| B-K | | | | 0-0 | 33-21-14 | L00774 | | RED | | | | | | SP02948 | | S | | 150-199, 275-299 |
| C-A | | | | 0-0 | 33-21-14 | L00272 | | BLK | | | | | | SP00946 | | 9 | | ALL |
| C-B | | | | 0-0 | 33-21-14 | L00272 | | BLK | | | | | | SP00948 | | 9 | | ALL |
| C-C | | | | 0-0 | 33-21-14 | L00272 | | WHT | | | | | | SP00950 | | 9 | | ALL |
| C-D | | | | 0-0 | 33-21-14 | L00272 | | WHT | | | | | | SP00952 | | 9 | | ALL |
| C-E | | | | 0-0 | 33-21-14 | L00272 | | RED | | | | | | SP02024 | | S | | ALL |
| D-A | | | | 0-0 | 33-21-14 | L00273 | | BLK | | | | | | SP00938 | | 9 | | ALL |
| D-B | | | | 0-0 | 33-21-14 | L00273 | | BLK | | | | | | SP00940 | | 9 | | ALL |
| D-C | | | | 0-0 | 33-21-14 | L00273 | | WHT | | | | | | SP00942 | | 9 | | ALL |
| D-D | | | | 0-0 | 33-21-14 | L00273 | | WHT | | | | | | SP00944 | | 9 | | ALL |
| D-E | | | | 0-0 | 33-21-14 | L00273 | | RED | | | | | | SP02026 | | S | | ALL |
| E-A | | | | 0-0 | 33-21-14 | L00276 | | BLK | | | | | | SP01042 | | 9 | | ALL |
| E-B | | | | 0-0 | 33-21-14 | L00276 | | BLK | | | | | | SP01044 | | 9 | | ALL |
| E-C | | | | 0-0 | 33-21-14 | L00276 | | WHT | | | | | | SP01046 | | 9 | | ALL |
| E-D | | | | 0-0 | 33-21-14 | L00276 | | WHT | | | | | | SP01048 | | 9 | | ALL |
| E-E | | | | 0-0 | 33-21-14 | L00276 | | RED | | | | | | SP02028 | | S | | ALL |
| F-A | | | | 0-0 | 33-21-14 | L00277 | | BLK | | | | | | SP01034 | | 9 | | ALL |
| F-B | | | | 0-0 | 33-21-14 | L00277 | | BLK | | | | | | SP01036 | | 9 | | ALL |
| F-C | | | | 0-0 | 33-21-14 | L00277 | | WHT | | | | | | SP01038 | | 9 | | ALL |
| F-D | | | | 0-0 | 33-21-14 | L00277 | | WHT | | | | | | SP01040 | | 9 | | ALL |
| F-E | | | | 0-0 | 33-21-14 | L00277 | | RED | | | | | | SP02030 | | S | | ALL |
| G-A | | | | 0-0 | 33-21-14 | L00280 | | BLK | | | | | | SP01058 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 21

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0824 | 286T0824 | | | CENTER AFT DIRECT,INDIRECT,GALLEY LIGHTING (continued) | | | | | | | | | | | |
| G-B | | | | | 0-0 | 33-21-14 | L00280 | | BLK | | SP01060 | | 9 | | ALL |
| G-C | | | | | 0-0 | 33-21-14 | L00280 | | WHT | | SP01062 | | 9 | | ALL |
| G-D | | | | | 0-0 | 33-21-14 | L00280 | | WHT | | SP01064 | | 9 | | ALL |
| G-E | | | | | 0-0 | 33-21-14 | L00280 | | RED | | SP02032 | | S | | 050-099, 150-199 |
| H-A | | | | | 0-0 | 33-21-14 | L00281 | | BLK | | SP01050 | | 9 | | ALL |
| H-B | | | | | 0-0 | 33-21-14 | L00281 | | BLK | | SP01052 | | 9 | | ALL |
| H-C | | | | | 0-0 | 33-21-14 | L00281 | | WHT | | SP01054 | | 9 | | ALL |
| H-D | | | | | 0-0 | 33-21-14 | L00281 | | WHT | | SP01056 | | 9 | | ALL |
| H-E | | | | | 0-0 | 33-21-14 | L00281 | | RED | | SP02034 | | S | | 050-099, 150-199 |
| J-A | | | | | 0-0 | 33-21-14 | L00269 | | BLK | | SP01066 | | 9 | | ALL |
| J-B | | | | | 0-0 | 33-21-14 | L00269 | | BLK | | SP01068 | | 9 | | ALL |
| J-C | | | | | 0-0 | 33-21-14 | L00269 | | WHT | | SP01070 | | 9 | | ALL |
| J-D | | | | | 0-0 | 33-21-14 | L00269 | | WHT | | SP01072 | | 9 | | ALL |
| J-E | | | | | 0-0 | 33-21-14 | L00269 | | RED | | SP02036 | | S | | ALL |
| K-A | | | | | 0-0 | 33-21-14 | L00268 | | BLK | | SP01074 | | 9 | | ALL |
| K-B | | | | | 0-0 | 33-21-14 | L00268 | | BLK | | SP01076 | | 9 | | ALL |
| K-C | | | | | 0-0 | 33-21-14 | L00268 | | WHT | | SP01078 | | 9 | | ALL |
| K-D | | | | | 0-0 | 33-21-14 | L00268 | | WHT | | SP01080 | | 9 | | ALL |
| K-E | | | | | 0-0 | 33-21-14 | L00268 | | RED | | SP02038 | | S | | ALL |
| W0828 | 286T0828 | | | R AFT LAV & DR WRN,MISC PWR | | | | | | | | | | | |
| 003 | 20 | | PA | | 9-10 | 33-26-21 | SP01582 | | | | D00814 | | 10 | | 275-299 |
| 007 | 20 | | PA | | 6-4 | 33-26-21 | D00814 | | 13 | S | L01027 | | S | C | * 275-299 |
| 009 | 20 | | PA | | 52-0 | 33-26-21 | D05096P | | 1 | | L01027 | | P | C | * 275-299 |
| 010 | 20 | | PA | | 9-8 | 33-26-21 | L00403 | | G | C | GD00020 | | A.. | 2 | 275-299 |
| 012 | 18 | | PA | | 0-6 | 33-26-11 | SM00009 | | | 9 | D00814 | | 6 | | 050-099, 275-299 |
| 013 | 22 | | PA | | 49-0 | 33-26-11 | D05096P | | 4 | | D00816 | | 15 | | 050-099 |
| 017 | 18 | | PA | | 39-9 | 38-32-16 | D00816 | | 20 | DK | SP03988 | | 9 | | 157 |
| 017 | 18 | | PA | | 39-9 | 38-32-16 | D00816 | | 20 | DK | SP03988 | | S | | 166-199 |
| 018 | 20 | | PA | | 9-3 | 33-26-11 | D00814 | | 1 | | GD00026 | | A.. | 2 | 050-099 |
| 018 | 20 | | PA | | 12-4 | 33-26-11 | D00814 | | 1 | | GD00026 | | A.. | 2 | 275-299 |
| 019 | 16 | | PA | | 9-3 | 38-13-11 | D00814 | | 2 | | GD00026 | | A.. | 2 | 050-099 |
| 019 | 16 | | PA | | 12-2 | 38-13-11 | D00814 | | 2 | | GD00026 | | A.. | 2 | 150-199 |
| 019 | 16 | | PA | | 12-4 | 38-13-11 | D00814 | | 2 | | GD00026 | | A.. | 2 | 275-299 |
| 021 | 22 | | PA | | 39-10 | 33-26-11 | D00814 | | 15 | | D05096P | | 18 | | 050-099 |
| 021 | 22 | | PA | | 60-4 | 33-26-11 | D00816 | | 15 | | D06742P | | 31 | | 150-199 |
| 021 | 22 | | PA | | 50-9 | 33-26-11 | D00814 | | 15 | | D05096P | | 4 | | 275-299 |
| 022 | 20 | | PA | | 39-10 | 33-26-11 | D00814 | | 17 | | D05096P | | 19 | | 050-099 |
| 022 | 20 | | PA | | 60-4 | 33-26-11 | D00816 | | 6 | | D06742P | | 15 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 22

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|------|------|---------|-------------|-----|---|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0828 | 286T0828 | | | R AFT LAV & DR WRN,MISC PWR (continued) | | | | | | | | | | | | | | | |
| 022 | 20 | | PA | | 50-9 | 33-26-11 | D00814 | | 17 | | | | | | D05096P | 5 | | | 275-299 |
| 024 | 22 | | PA | | 31-8 | 33-25-11 | D00816 | | 7 | | | | | | SM00031 | | S | | 050-099 |
| 024 | 22 | | PA | | 84-6 | 33-25-11 | D00816 | | 7 | | | | | | SP00327 | | S | | 150-199 |
| 025 | 16 | | PA | | 22-6 | 38-13-11 | SM00019 | | | | 9 | | | | D00814 | | 8 | | 050-099 |
| 025 | 16 | | PA | | 47-5 | 38-13-11 | D05096P | | 11 | | FL | | | | SM00020 | | S | | 150-199 |
| 025 | 16 | | PA | | 50-9 | 38-13-11 | D05096P | | 11 | | | | | | D00814 | | 8 | | 275-299 |
| 027 | 22 | | PA | | 22-6 | 33-25-11 | D00814 | | 7 | | | | | | SM00031 | | S | | 050-099 |
| 027 | 22 | | PA | | 75-5 | 33-25-11 | D00814 | | 7 | | | | | | SP00329 | | S | | 150-199 |
| 027 | 22 | | PA | | 19-7 | 33-25-11 | D00814 | | 7 | | | | | | B00148 | | HI | C | 275-299 |
| 028 | 22 | | PA | | 22-6 | 33-25-11 | D00814 | | 9 | | | | | | SM00033 | | S | | 050-099 |
| 028 | 22 | | PA | | 75-5 | 33-25-11 | D00814 | | 9 | | | | | | SP03694 | | 9 | | 150-199 |
| 028 | 22 | | PA | | 50-9 | 33-25-11 | D00814 | | 9 | | | | | | D05096P | | 7 | | 275-299 |
| 029 | 22 | | PA | | 19-5 | 33-25-11 | D00814 | | 25 | | | | | | SP03698 | | S | | 050-099 |
| 029 | 22 | | PA | | 75-5 | 33-25-11 | D00814 | | 25 | | | | | | SP03698 | | S | | 150-199 |
| 029 | 22 | | PA | | 9-10 | 33-25-11 | D00814 | | 25 | | | | | | SP00574 | | S | | 275-299 |
| 030 | 20 | | PA | | 9-3 | 33-25-11 | D00814 | | 26 | | | | | | GD00026 | | D.. | 2 | 050-099 |
| 030 | 20 | | PA | | 12-2 | 33-25-11 | D00814 | | 26 | | | | | | GD00026 | | D.. | 2 | 150-199 |
| 030 | 20 | | PA | | 12-4 | 33-25-11 | D00814 | | 26 | | | | | | GD00026 | | D.. | 2 | 275-299 |
| 038 | 22 | | PA | | 52-7 | 38-32-13 | D05096P | | 12 | | | | | | SP00606 | | S | | 050-099 |
| 038 | 22 | | PA | | 58-7 | 38-32-13 | D05096P | | 12 | | | | | | SP00606 | | S | | 150-156, 162-165 |
| 038 | 22 | | PA | | 58-7 | 38-32-16 | D05096P | | 12 | | | | | | SP00606 | | S | | 157, 166-199 |
| 038 | 22 | | PA | | 59-0 | 38-32-13 | D05096P | | 12 | | | | | | SP00606 | | S | | 275-276 |
| 038 | 22 | | PA | | 59-0 | 38-32-16 | D05096P | | 12 | | | | | | SP00606 | | S | | 277-299 |
| 041 | 18 | | PA | | 21-9 | 38-32-13 | D00814 | | 20 | | DK | | | | SP01700 | | S | | 050-099 |
| 041 | 18 | | PA | | 16-8 | 38-32-13 | D00814 | | 20 | | DK | | | | SP01700 | | S | | 150-156, 162-165 |
| 041 | 18 | | PA | | 16-8 | 38-32-16 | D00814 | | 20 | | DK | | | | SP01700 | | S | | 157, 166-199 |
| 041 | 18 | | PA | | 18-0 | 38-32-13 | D00814 | | 20 | | DK | | | | SP01700 | | S | | 275-276 |
| 041 | 18 | | PA | | 18-0 | 38-32-16 | D00814 | | 20 | | DK | | | | SP01700 | | S | | 277-299 |
| 042 | 22 | | PA | | 21-9 | 38-32-13 | D00814 | | 21 | | | | | | SP00606 | | S | | 050-099 |
| 042 | 22 | | PA | | 16-8 | 38-32-13 | D00814 | | 21 | | | | | | SP00606 | | S | | 150-156, 162-165 |
| 042 | 22 | | PA | | 16-8 | 38-32-16 | D00814 | | 21 | | | | | | SP00606 | | S | | 157, 166-199 |
| 042 | 22 | | PA | | 18-0 | 38-32-13 | D00814 | | 21 | | | | | | SP00606 | | S | | 275-276 |
| 042 | 22 | | PA | | 18-0 | 38-32-16 | D00814 | | 21 | | | | | | SP00606 | | S | | 277-299 |
| 043 | 20 | | PA | | 9-3 | 38-32-13 | D00814 | | 18 | | | | | | GD00026 | | D.. | 2 | 050-099 |
| 043 | 20 | | PA | | 12-2 | 38-32-13 | D00814 | | 18 | | | | | | GD00026 | | D.. | 2 | 150-156, 162-165 |
| 043 | 20 | | PA | | 12-2 | 38-32-16 | D00814 | | 18 | | | | | | GD00026 | | D.. | 2 | 157, 166-199 |
| 043 | 20 | | PA | | 12-4 | 38-32-13 | D00814 | | 18 | | | | | | GD00026 | | D.. | 2 | 275-276 |
| 043 | 20 | | PA | | 12-4 | 38-32-16 | D00814 | | 18 | | | | | | GD00026 | | D.. | 2 | 277-299 |
| 044 | 20 | | PA | | 9-3 | 38-32-13 | D00814 | | 19 | | | | | | GD00026 | | S.. | 2 | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 23

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0828 | 286T0828 | | | R AFT LAV & DR WRN,MISC PWR (continued) | | | | | | | | | | | | | |
| 044 | 20 | | PA | 12-2 | 38-32-13 | D00814 | | 19 | | | | | GD00026 | S.. | 2 | | 150-156, 162-165 |
| 044 | 20 | | PA | 12-2 | 38-32-16 | D00814 | | 19 | | | | | GD00026 | S.. | 2 | | 157, 166-199 |
| 044 | 20 | | PA | 12-4 | 38-32-13 | D00814 | | 19 | | | | | GD00026 | S.. | 2 | | 275-276 |
| 044 | 20 | | PA | 12-4 | 38-32-16 | D00814 | | 19 | | | | | GD00026 | S.. | 2 | | 277-299 |
| 045 | 20 | | PA | 18-5 | 33-24-11 | D05096P | | 10 | | | | | SM00005 | | S | | 050-099 |
| 045 | 20 | | PA | 47-5 | 33-24-11 | D05096P | | 10 | | | | | SM00005 | | S | | 150-199 |
| 047 | 20 | | PA | 22-6 | 33-24-11 | D00814 | | 12 | | | | | SM00005 | | S | | 050-099 |
| 047 | 20 | | PA | 3-11 | 33-24-11 | D00814 | | 12 | | | | | SM00005 | | S | | 150-199 |
| 047 | 20 | | PA | 50-9 | 33-24-11 | D00814 | | 12 | | | | | D05096P | | 10 | | 275-299 |
| 048 | 18 | | PA | 52-7 | 38-32-13 | D05096P | | 13 | DL | | | | SP01700 | | S | | 050-099 |
| 048 | 18 | | PA | 58-7 | 38-32-13 | D05096P | | 13 | DL | | | | SP01700 | | S | | 150-156, 162-165 |
| 048 | 18 | | PA | 58-7 | 38-32-16 | D05096P | | 13 | DL | | | | SP01700 | | S | | 157, 166-199 |
| 048 | 18 | | PA | 59-0 | 38-32-13 | D05096P | | 13 | | | | | SP01700 | | S | | 275-276 |
| 048 | 18 | | PA | 59-0 | 38-32-16 | D05096P | | 13 | | | | | SP01700 | | S | | 277-299 |
| 050 | 20 | | PA | 6-5 | 33-26-21 | L01027 | | G | C | | | | GD01046 | A.. | E | | 275-299 |
| 051 | 20 | | PA | 20-1 | 33-26-21 | L01027 | | S | C | * | | | L00403 | S | C | | 275-299 |
| 053 | 20 | | PA | 20-1 | 33-26-21 | L01027 | | P | C | * | | | L00403 | P | C | | 275-299 |
| 070 | 20 | | PA | 49-0 | 33-26-11 | D05096P | | 5 | | | | | D00816 | | 17 | | 050-099 |
| 099 | 22 | | PA | 42-0 | 33-26-11 | D05096P | | 3 | | | | | SM00009 | | 9 | | 050-099 |
| 099 | 22 | | PA | 60-4 | 33-26-11 | D06742P | | 6 | | | | | D00816 | | 17 | | 150-199 |
| 099 | 22 | | PA | 50-9 | 33-26-11 | D05096P | | 3 | | | | | SM00009 | | 9 | | 275-299 |
| 101 | 22 | | PA | 59-0 | 33-26-11 | D05096P | | 11 | | | | | SM00011 | | 9 | | 050-099 |
| 102 | 22 | | PA | 87-10 | 33-25-11 | SP00329 | | | S | | | | B00148 | HI | C | | 150-199 |
| 104 | 16 | | PA | 18-5 | 38-13-11 | D05096P | | 21 | | | | | SM00019 | | 9 | | 050-099 |
| 104 | 20 | | PA | 47-5 | 25-42-11 | SM00010 | | | S | | | | D05096P | | 14 | | 150-199 |
| 105 | 20 | | PA | 50-9 | 33-26-11 | D00814 | | 15 | | | | | D06742P | | 4 | | 150-199 |
| 106 | 20 | | PA | 50-9 | 33-26-11 | D00814 | | 6 | | | | | D06742P | | 5 | | 150-199 |
| 107 | 20 | | PA | 11-11 | 33-26-11 | D00816 | | 1 | | | | | GD00020 | A.. | 2 | | 150-199 |
| 108 | 20 | | PA | 18-5 | 25-42-11 | D05096P | | 14 | | | | | SM00010 | | 9 | | 050-099 |
| 108 | 20 | | PA | 50-9 | 25-42-11 | D05096P | | 14 | | | | | D00814 | | 29 | | 275-299 |
| 109 | 20 | | PA | 26-1 | 25-42-11 | D06904P | | 10 | | | | | SM00010 | | 9 | | 050-099 |
| 109 | 20 | | PA | 19-5 | 25-42-11 | D13492 | | 10 | | | | | SM00010 | | S | | 150-157 |
| 109 | 20 | | PA | 13-9 | 25-42-11 | D06904P | | 10 | | | | | SM00010 | | S | | 162-199 |
| 110 | 20 | | PA | 34-4 | 25-42-11 | D06906P | | 10 | | | | | SM00010 | | 9 | | 050-099 |
| 110 | 20 | | PA | 20-11 | 25-42-11 | D13494 | | 10 | | | | | SM00010 | | S | | 150-157 |
| 110 | 20 | | PA | 19-4 | 25-42-11 | D06906P | | 10 | | | | | SM00010 | | S | | 162-199 |
| 111 | 20 | | PA | 10-3 | 33-26-11 | D00816 | | 1 | | | | | GD00020 | A.. | 2 | | 050-099 |
| 112 | 16 | | PA | 10-3 | 38-13-11 | D00816 | | 2 | | | | | GD00020 | A.. | 2 | | 050-099 |
| 115 | 16 | | PA | 3-11 | 38-13-11 | D00814 | | 8 | | | | | SM00020 | | S | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W0820
Page 24
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0828 | 286T0828 | | | R AFT LAV & DR WRN,MISC PWR (continued) | | | | | | | | | | | | | |
| 116 | 18 | | PA | 0-6 | 33-26-11 | SM00011 | | | | | 9 | | | D00816 | 6 | | 050-099 |
| 117 | 22 | | PA | 96-11 | 33-25-11 | B00147 | | | | | HI | | | SP00327 | | S | 150-199 |
| 118 | 16 | | PA | 31-8 | 38-13-11 | D00816 | | | | | 8 | | | SM00019 | | 9 | 050-099 |
| 119 | 22 | | PA | 31-8 | 33-25-11 | D00816 | | | | | 9 | | | SM00033 | | S | 050-099 |
| 119 | 22 | | PA | 84-6 | 33-25-11 | D00816 | | | | | 9 | | | SP03694 | | 9 | 150-199 |
| 121 | 16 | | PA | 15-2 | 38-13-11 | D00816 | | | | | 8 | | | SM00020 | | S | 150-199 |
| 122 | 20 | | PA | 31-8 | 33-24-11 | D00816 | | | | | 12 | | | SM00005 | | S | 050-099 |
| 122 | 20 | | PA | 15-2 | 33-24-11 | D00816 | | | | | 12 | | | SM00005 | | S | 150-199 |
| 126 | 16 | | PA | 25-1 | 38-13-11 | D00816 | | | | | 2 | | | GD00026 | A.. | 2 | 150-199 |
| 128 | 20 | | PA | 10-3 | 38-32-12 | D00816 | | | | | 18 | | | GD00020 | D.. | 2 | 050-099 |
| 128 | 20 | | PA | 11-11 | 38-32-12 | D00816 | | | | | 18 | | | GD00020 | D.. | 2 | 150-156, 162-165 |
| 128 | 20 | | PA | 11-11 | 38-32-16 | D00816 | | | | | 18 | | | GD00020 | D.. | 2 | 157, 166-199 |
| 129 | 20 | | PA | 10-3 | 38-32-12 | D00816 | | | | | 19 | | | GD00020 | S.. | 2 | 050-099 |
| 129 | 20 | | PA | 11-11 | 38-32-12 | D00816 | | | | | 19 | | | GD00020 | S.. | 2 | 150-156, 162-165 |
| 129 | 20 | | PA | 11-11 | 38-32-16 | D00816 | | | | | 19 | | | GD00020 | S.. | 2 | 157, 166-199 |
| 130 | 18 | | PA | 49-0 | 38-32-12 | D06742P | | | | | 7 | DL | | D00816 | 20 | DK | 050-099 |
| 130 | 18 | | PA | 60-4 | 38-32-12 | D06742P | | | | | 7 | DL | | D00816 | 20 | DK | 150-156, 162-165 |
| 130 | 18 | | PA | 72-7 | 38-32-16 | D06742P | | | | | 7 | DL | | SP03988 | | 9 | 157 |
| 130 | 18 | | PA | 72-7 | 38-32-16 | D06742P | | | | | 7 | DL | | SP03988 | | S | 166-199 |
| 131 | 22 | | PA | 29-2 | 38-32-12 | D00816 | | | | | 21 | | | SP01628 | | 9 | 050-099 |
| 131 | 20 | | PA | 39-9 | 38-32-12 | D00816 | | | | | 21 | | | SP01628 | | 9 | 150-156, 162-165 |
| 131 | 20 | | PA | 39-9 | 38-32-16 | D00816 | | | | | 21 | | | SP01628 | | 9 | 157, 166-199 |
| 133 | 18 | | PA | 59-4 | 26-13-11 | D13552 | | | | | 10 | DL | | D06742P | 2 | DL | 050-099 |
| 133 | 18 | | PA | 69-4 | 26-13-11 | D13552 | | | | | 10 | DL | | D06742P | 2 | DL | 150-199 |
| 134 | 20 | | PA | 59-4 | 26-13-11 | D13552 | | | | | 20 | | | D06742P | 29 | | 050-099 |
| 134 | 20 | | PA | 69-4 | 26-13-11 | D13552 | | | | | 20 | | | D06742P | 29 | | 150-199 |
| 135 | 22 | | PA | 28-7 | 33-25-11 | SP00574 | | | | | | | S | D00816 | 25 | | 050-099 |
| 135 | 22 | | PA | 84-6 | 33-25-11 | D00816 | | | | | 25 | | | SP00572 | | 9 | 150-199 |
| 137 | 20 | | PA | 59-4 | 26-13-11 | D13552 | | | | | 11 | | | D06742P | 16 | | 050-099 |
| 137 | 20 | | PA | 69-4 | 26-13-11 | D13552 | | | | | 11 | | | D06742P | 16 | | 150-199 |
| 138 | 20 | | PA | 69-4 | 26-13-11 | D13552 | | | | | 24 | | | D06742P | 17 | | 150-199 |
| 139 | 20 | | PA | 59-4 | 26-13-11 | D13552 | | | | | 23 | | | D06742P | 18 | | 050-099 |
| 139 | 20 | | PA | 69-4 | 26-13-11 | D13552 | | | | | 23 | | | D06742P | 18 | | 150-199 |
| 140 | 20 | | PA | 41-6 | 26-13-11 | D13552 | | | | | 22 | | | SM00021 | | 9 | 050-099 |
| 140 | 20 | | PA | 21-3 | 26-13-11 | D13552 | | | | | 22 | | | SM00021 | | S | 150-199 |
| 141 | 20 | | PA | 41-6 | 26-13-11 | D13552 | | | | | 9 | | | SM00022 | | 9 | 050-099 |
| 141 | 20 | | PA | 21-3 | 26-13-11 | D13552 | | | | | 9 | | | SM00022 | | S | 150-199 |
| 142 | 20 | | PA | 41-6 | 26-13-11 | D13552 | | | | | 7 | | | SM00023 | | 9 | 050-099 |
| 142 | 20 | | PA | 21-3 | 26-13-11 | D13552 | | | | | 7 | | | SM00023 | | S | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 25

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0828 | 286T0828 | | | R AFT LAV & DR WRN,MISC PWR (continued) | | | | | | | | | | | | | |
| 143 | 20 | PA | | 31-11 | 26-13-12 | D13552 | | 12 | | | | | D06904P | 1 | | | 050-099 |
| 143 | 20 | PA | | 23-2 | 26-13-11 | D13552 | | 12 | | | | | D13492 | 1 | | | 150-157 |
| 143 | 20 | PA | | 36-11 | 26-13-12 | D13552 | | 12 | | | | | D06904P | 1 | | | 162-199 |
| 144 | 20 | PA | | 40-7 | 26-13-12 | D13552 | | 5 | | | | | D06906P | 1 | | | 050-099 |
| 144 | 20 | PA | | 34-11 | 26-13-11 | D13552 | | 5 | | | | | D13494 | 1 | | | 150-157 |
| 144 | 20 | PA | | 40-9 | 26-13-12 | D13552 | | 5 | | | | | D06906P | 1 | | | 162-199 |
| 145 | 20 | PA | | 35-5 | 26-13-11 | D13552 | | 21 | | | | | GD00026 | S.. | 2 | | 050-099 |
| 145 | 20 | PA | | 34-2 | 26-13-11 | D13552 | | 21 | | | | | GD00026 | S.. | 2 | | 150-199 |
| 146 | 20 | PA | | 35-5 | 26-13-11 | D13552 | | 8 | | | | | GD00026 | D.. | 2 | | 050-099 |
| 146 | 20 | PA | | 34-2 | 26-13-11 | D13552 | | 8 | | | | | GD00026 | D.. | 2 | | 150-199 |
| 147 | 20 | PA | | 16-6 | 26-13-11 | SM00021 | | | S | | | | D13492 | 2 | | | 150-157 |
| 147 | 20 | PA | | 16-8 | 26-13-12 | SM00021 | | | S | | | | D06904P | 2 | | | 162-199 |
| 148 | 20 | PA | | 18-4 | 26-13-11 | D06742P | | 19 | | | | | SM00021 | | 9 | | 050-099 |
| 148 | 20 | PA | | 48-8 | 26-13-11 | SM00021 | | | S | | | | D06742P | 19 | | | 150-199 |
| 149 | 20 | PA | | 16-6 | 26-13-11 | SM00022 | | | S | | | | D13492 | 3 | | | 150-157 |
| 149 | 20 | PA | | 16-8 | 26-13-12 | SM00022 | | | S | | | | D06904P | 3 | | | 162-199 |
| 150 | 20 | PA | | 18-4 | 26-13-11 | D06742P | | 20 | | | | | SM00022 | | 9 | | 050-099 |
| 150 | 20 | PA | | 48-8 | 26-13-11 | SM00022 | | | S | | | | D06742P | 20 | | | 150-199 |
| 151 | 20 | PA | | 16-6 | 26-13-11 | SM00023 | | | S | | | | D13492 | 4 | | | 150-157 |
| 151 | 20 | PA | | 16-8 | 26-13-12 | SM00023 | | | S | | | | D06904P | 4 | | | 162-199 |
| 152 | 20 | PA | | 18-4 | 26-13-11 | D06742P | | 24 | | | | | SM00023 | | 9 | | 050-099 |
| 152 | 20 | PA | | 48-8 | 26-13-11 | SM00023 | | | S | | | | D06742P | 24 | | | 150-199 |
| 153 | 20 | PA | | 18-0 | 26-13-11 | SM00023 | | | S | | | | D13494 | 4 | | | 150-157 |
| 153 | 20 | PA | | 20-6 | 26-13-12 | SM00023 | | | S | | | | D06906P | 4 | | | 162-199 |
| 154 | 20 | PA | | 18-0 | 26-13-11 | SM00022 | | | S | | | | D13494 | 3 | | | 150-157 |
| 154 | 20 | PA | | 20-6 | 26-13-12 | SM00022 | | | S | | | | D06906P | 3 | | | 162-199 |
| 155 | 20 | PA | | 18-0 | 26-13-11 | SM00021 | | | S | | | | D13494 | 2 | | | 150-157 |
| 155 | 20 | PA | | 20-6 | 26-13-12 | SM00021 | | | S | | | | D06906P | 2 | | | 162-199 |
| 156 | 20 | PA | | 50-9 | 33-26-11 | D00814 | | 17 | | | | | D06742P | 3 | | | 150-199 |
| 175 | 20 | PA | | 10-3 | 33-25-11 | D00816 | | 26 | | | | | GD00020 | D.. | 2 | | 050-099 |
| 175 | 20 | PA | | 11-11 | 33-25-11 | D00816 | | 26 | | | | | GD00020 | D.. | 2 | | 150-199 |
| 183 | 24 | PK | | 43-5 | 33-21-31 | D06904P | | 5 | | | | | D05096P | 37 | | | 050-099 |
| 183 | 24 | PK | | 60-8 | 33-21-31 | D06904P | | 5 | | | | | D05096P | 37 | | | 162-199 |
| 184 | 20 | PA | | 17-6 | 33-21-31 | D06904P | | 6 | | | | | GD00026 | A.. | 2 | | 050-099 |
| 184 | 20 | PA | | 23-1 | 33-21-31 | D06904P | | 6 | | | | | GD00026 | A.. | 2 | | 162-199 |
| 185 | 24 | PK | | 26-1 | 33-21-31 | D06904P | | 7 | | | | | SM00029 | | 9 | | 050-099 |
| 185 | 24 | PK | | 13-9 | 33-21-31 | D06904P | | 7 | | | | | SM00029 | | 9 | | 162 |
| 185 | 24 | PK | | 13-9 | 33-21-31 | D06904P | | 7 | | | | | SM00029 | | S | | 163-199 |
| 187 | 24 | PK | | 18-5 | 33-21-31 | D05096P | | 38 | | | | | SM00029 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 26

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0828 | 286T0828 | | | R AFT LAV & DR WRN,MISC PWR (continued) | | | | | | | | | | | | | | |
| 187 | 24 | | PK | 47-5 | 33-21-31 | SM00029 | | | | | 9 | | | D05096P | 38 | | | 162 |
| 187 | 24 | | PK | 47-5 | 33-21-31 | SM00029 | | | | | S | | | D05096P | 38 | | | 163-199 |
| 188 | 24 | | PK | 52-2 | 33-21-31 | D06906P | | | 5 | | | | | D05096P | 39 | | | 050-099 |
| 188 | 24 | | PK | 63-11 | 33-21-31 | D06906P | | | 5 | | | | | D05096P | 39 | | | 162-199 |
| 189 | 20 | | PA | 28-6 | 33-21-31 | D06906P | | | 6 | | | | | GD00026 | A.. | 2 | | 050-099 |
| 189 | 20 | | PA | 29-3 | 33-21-31 | D06906P | | | 6 | | | | | GD00026 | A.. | 2 | | 162-199 |
| 190 | 24 | | PK | 34-4 | 33-21-31 | D06906P | | | 7 | | | | | SM00029 | | 9 | | 050-099 |
| 190 | 24 | | PK | 19-4 | 33-21-31 | D06906P | | | 7 | | | | | SM00029 | | 9 | | 162 |
| 190 | 24 | | PK | 19-4 | 33-21-31 | D06906P | | | 7 | | | | | SM00029 | | S | | 163-199 |
| 192 | 20 | | PA | 26-1 | 26-13-12 | D06904P | | | 2 | | | | | SM00021 | | 9 | | 050-099 |
| 193 | 20 | | PA | 26-1 | 26-13-12 | D06904P | | | 3 | | | | | SM00022 | | 9 | | 050-099 |
| 194 | 20 | | PA | 26-1 | 26-13-12 | D06904P | | | 4 | | | | | SM00023 | | 9 | | 050-099 |
| 196 | 20 | | PA | 34-4 | 26-13-12 | D06906P | | | 2 | | | | | SM00021 | | 9 | | 050-099 |
| 197 | 20 | | PA | 34-4 | 26-13-12 | D06906P | | | 3 | | | | | SM00022 | | 9 | | 050-099 |
| 198 | 20 | | PA | 34-4 | 26-13-12 | D06906P | | | 4 | | | | | SM00023 | | 9 | | 050-099 |
| 201B | 22 | | PB | A | 49-9 | 23-31-14 | D05096P | | | 9 | | | | SP01698 | | S | | 050-099 |
| 201B | 22 | | PB | A | 51-8 | 23-31-14 | D05096P | | | 9 | | | | SP01698 | | S | | 150-199, 275-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-14 | D05096P | | | 8 | | | | SP01696 | | S | | ALL |
| 202B | 22 | | PB | B | 28-7 | 23-31-14 | D00816 | | | 5 | | | | SP01698 | | S | | 050-099 |
| 202B | 22 | | PB | D | 13-5 | 23-31-14 | SP01698 | | | | | | | D00816 | | 5 | | 150-199 |
| 202R | 22 | | PB | B | 0-0 | 23-31-14 | D00816 | | | 16 | | | | SP01696 | | S | | 050-099 |
| 202R | 22 | | PB | D | 0-0 | 23-31-14 | SP01696 | | | | | | | D00816 | | 16 | | 150-199 |
| 203B | 22 | | PB | C | 19-5 | 23-31-14 | SP01698 | | | | | | | D00814 | | 5 | | 050-099 |
| 203B | 22 | | PB | C | 9-10 | 23-31-14 | SP01698 | | | | | | | D00814 | | 5 | | 150-199, 275-299 |
| 203R | 22 | | PB | C | 0-0 | 23-31-14 | SP01696 | | | | | | | D00814 | | 16 | | ALL |
| 211 | 20 | | PA | 7-11 | 26-13-12 | D06904P | | | 8 | | | | | SM00034 | | 9 | | 050-099 |
| 212 | 20 | | PA | 25-1 | 26-13-12 | D13552 | | | 1 | | | | | SM00034 | | 9 | | 050-099 |
| 213 | 20 | | PA | 18-2 | 26-13-12 | D06906P | | | 8 | | | | | SM00034 | | 9 | | 050-099 |
| 500 | 20 | | PA | 39-10 | 33-26-21 | D05096P | | | 2 | | | | | D00814 | | 10 | | 050-099 |
| 500 | 20 | | PA | 60-4 | 33-26-21 | D00816 | | | 10 | | | | | D05096P | | 2 | | 162-199 |
| 501 | 20 | | PA | 18-4 | 33-26-21 | D00814 | | | 13 | | | | | D00816 | | 10 | | 050-099 |
| 501 | 20 | | PA | 18-6 | 33-26-21 | D00814 | | | 10 | | | | | D00816 | | 13 | | 162-199 |
| 507 | 20 | | PA | 12-1 | 26-13-12 | D13930 | | | = 1 | | | | | SM00022 | | S | | 164-199 |
| 508 | 20 | | PA | 31-7 | 26-13-12 | D13952 | | | = 1 | | | | | D06906P | | 12 | | 164-199 |
| 510 | 20 | | PA | 7-2 | 26-13-12 | D13932 | | | = 1 | | | | | SM00022 | | S | | 164-199 |
| 511 | 20 | | PA | 16-4 | 26-13-12 | D13954 | | | = 1 | | | | | D06904P | | 12 | | 164-199 |
| 513 | 20 | | PA | 13-9 | 26-13-12 | D06904P | | | 8 | | | | | SM00034 | | S | | 162-199 |
| 514 | 20 | | PA | 24-2 | 26-13-12 | D13552 | | | 1 | | | | | SM00034 | | S | | 150, 152-199 |
| 515 | 20 | | PA | 19-4 | 26-13-12 | D06976J | | | 8 | | | | | SM00034 | | S | | 150, 152-157 |

WIRE LIST

D280T132

91-21-11

Section W0820

Page 27

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0828 | 286T0828 | | | R AFT LAV & DR WRN,MISC PWR (continued) | | | | | | | | | | | | |
| 515 | 20 | | PA | | 19-4 | 26-13-12 | D06906P | | 8 | | SM00034 | | S | | 162-199 | |
| 603 | 22 | | PA | | 50-8 | 38-32-12 | D06742P | | 1 | | SP01628 | | 9 | | 050-099 | |
| 603 | 20 | | PA | | 72-7 | 38-32-12 | D06742P | | 1 | | SP01628 | | 9 | | 150-156, 162-165 | |
| 603 | 20 | | PA | | 72-7 | 38-32-16 | D06742P | | 1 | | SP01628 | | 9 | | 157, 166-199 | |
| 607 | 22 | | PA | | 49-9 | 33-25-11 | SP03992 | | | S | D05096P | 34 | | | 050-099 | |
| 608 | 22 | | PA | | 49-9 | 33-25-11 | SP00574 | | | S | D05096P | 26 | | | 050-099 | |
| 609 | 22 | | PA | | 18-5 | 33-25-11 | D05096P | | 6 | | SM00031 | | S | | 050-099 | |
| 610 | 22 | | PA | | 18-5 | 33-25-11 | D05096P | | 7 | | SM00033 | | S | | 050-099 | |
| 611 | 22 | | PA | | 49-9 | 33-25-11 | D05096P | | 28 | | SP03698 | | S | | 050-099 | |
| 612 | 22 | | PA | | 43-4 | 21-66-31 | D06742P | | 8 | | D06904P | 9 | | | 050-099 | |
| 612 | 22 | | PA | | 60-8 | 21-66-31 | D06742P | | 8 | | D06976J | 9 | | | 150, 152-157 | |
| 612 | 22 | | PA | | 60-8 | 21-66-31 | D06742P | | 8 | | D06904P | 9 | | | 162-199 | |
| 613 | 22 | | PA | | 43-4 | 21-66-31 | D06742P | | 9 | | D06904P | 11 | | | 050-099 | |
| 613 | 22 | | PA | | 60-8 | 21-66-31 | D06742P | | 9 | | D06976J | 11 | | | 150, 152-157 | |
| 613 | 22 | | PA | | 60-8 | 21-66-31 | D06742P | | 9 | | D06904P | 11 | | | 162-199 | |
| 614 | 22 | | PA | | 52-1 | 21-66-41 | D06742P | | 11 | | D06906P | 9 | | | 050-099 | |
| 614 | 22 | | PA | | 63-11 | 21-66-41 | D06742P | | 11 | | D06906P | 9 | | | 150, 152-199 | |
| 615 | 22 | | PA | | 52-1 | 21-66-41 | D06742P | | 10 | | D06906P | 11 | | | 050-099 | |
| 615 | 22 | | PA | | 63-11 | 21-66-41 | D06742P | | 10 | | D06906P | 11 | | | 150, 152-199 | |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|-------------------------|----------|--------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0832 | 286T0832 | | | EMERGENCY LIGHTS | | | | | | | | | | | |
| 001 | 16 | PA | | 8-0 | 33-51-11 | D10718 | | 1 | FM | | GD00017 | D.. | 2 | | ALL |
| 002 | 20 | PA | | 29-0 | 33-51-11 | D10718 | | 2 | | | D06410P | 2 | | | ALL |
| 003 | 22 | PA | | 29-0 | 33-51-11 | D10718 | | 3 | | | D06410P | 3 | | | ALL |
| 004 | 22 | PA | | 29-0 | 33-51-11 | D10718 | | 4 | | | D06410P | 4 | | | ALL |
| 005 | 22 | PA | | 1-0 | 33-51-11 | D10718 | | 5 | | | D10718 | 6 | | | ALL |
| 007 | 20 | PA | | 8-0 | 33-51-11 | D10718 | | 7 | | | GD00017 | S.. | 2 | | ALL |
| 008 | 22 | PA | | 29-0 | 33-51-11 | D10718 | | 8 | | | D06410P | 8 | | | ALL |
| 009 | 16 | PA | | 14-0 | 33-51-14 | D10718 | | 9 | FM | | L00312 | 1 | C | | 050-099, 162-199 |
| 009 | 16 | PA | | 14-0 | 33-51-14 | D10718 | | 9 | FM | | L00312 | 1 | C | * | 150-157, 275-299 |
| 010 | 18 | PA | | 27-0 | 33-51-14 | D10718 | | 10 | DK | | L00287 | 1 | C | | 050-099, 150-199 |
| 010 | 16 | PA | | 27-0 | 33-51-14 | D10718 | | 10 | FM | | L00287 | 1 | C | * | 275-299 |
| 011 | 20 | PA | | 30-0 | 33-51-12 | D10718 | | 11 | | | L00288 | 1 | C | | 050-099 |
| 012 | 20 | PA | | 34-0 | 33-51-12 | D10718 | | 12 | | | L00289 | 1 | C | | 050-099 |
| 015 | 20 | PA | | 21-0 | 33-51-13 | D10718 | | 13 | | | L00611 | 1 | C | | 050-099 |
| 016 | 20 | PA | | 12-0 | 33-51-13 | L00611 | | 2 | C | | GD00760 | D.. | 2 | | 050-099 |
| 018 | 18 | PA | | 19-0 | 33-51-12 | L00289 | | 2 | C | | GD01114 | D.. | 2 | | 050-099 |
| 019 | 20 | PA | | 8-0 | 33-51-13 | L00313 | | 2 | C | | GD00760 | D.. | 2 | | 050-099 |
| 020 | 22 | PA | | 1-0 | 33-51-14 | D10718 | | 20 | | | D10718 | 24 | | | ALL |
| 021 | 20 | PA | | 11-0 | 33-51-14 | L00312 | | 1 | C | * | D11718 | =1 | | | 275-299 |
| 022 | 20 | PA | | 5-0 | 33-51-14 | D11720 | | =1 | | | GD00017 | D.. | 2 | | 275-299 |
| 023 | 20 | PA | | 13-0 | 33-51-14 | L00287 | | 1 | C | * | D11722 | =1 | | | 275-299 |
| 024 | 20 | PA | | 11-0 | 33-51-14 | D11724 | | =1 | | | GD01236 | D.. | 2 | | 275-299 |
| 027 | 16 | PA | | 5-0 | 33-51-14 | L00287 | | 2 | C | | GD01236 | D.. | 2 | | 050-099 |
| 027 | 16 | PA | | 7-0 | 33-51-14 | L00287 | | 2 | C | | GD01236 | D.. | 2 | | 150-199, 275-299 |
| 029 | 20 | PA | | 8-0 | 33-51-14 | L00312 | | 2 | C | | GD00002 | D.. | 2 | | ALL |
| 030 | 16 | PA | | 18-0 | 33-51-14 | L00312 | | 1 | C | * | L00324 | 1 | C | | 150-157 |
| 031 | 16 | PA | | 6-0 | 33-51-14 | L00324 | | 2 | C | | GD04194 | D.. | 2 | | 150-157 |
| 032 | 20 | PA | | 32-0 | 33-51-12 | D10718 | | 16 | | | L00290 | 1 | C | | 050-099 |
| 033 | 20 | PA | | 4-0 | 33-51-12 | L00290 | | 2 | C | | GD01114 | D.. | 2 | | 050-099 |
| 034 | 20 | PA | | 12-0 | 33-51-12 | L00288 | | 2 | C | | GD01236 | D.. | 2 | | 050-099 |
| 035 | 20 | PA | | 29-0 | 33-51-13 | D10718 | | 15 | | | L00314 | 1 | C | | 050-099 |
| 036 | 20 | PA | | 7-0 | 33-51-13 | L00314 | | 2 | C | | GD03932 | D.. | 2 | | 050-099 |
| 037 | 22 | PA | | 19-0 | 33-51-13 | D10718 | | 14 | | | L00313 | 1 | C | | 050-099 |
| W0834 | 286T0834 | | | EMERGENCY LIGHTS | | | | | | | | | | | |
| 001 | 20 | PA | | 3-0 | 33-51-11 | D10720 | | 1 | | | GD04676 | D.. | E | | 050-099 |
| 001 | 20 | PA | | 2-7 | 33-51-11 | D10720 | | 1 | | | GD04676 | D.. | E | | 150-199, 275-299 |
| 002 | 20 | PA | | 67-0 | 33-51-11 | D10720 | | 2 | | | D06412P | 2 | | | 050-099 |
| 002 | 20 | PA | | 73-6 | 33-51-11 | D10720 | | 2 | | | D06412P | 2 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0830

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0834 | 286T0834 | | | EMERGENCY LIGHTS (continued) | | | | | | | | | | | | | | |
| 003 | 22 | | PA | 67-0 | 33-51-11 | D10720 | | | | 3 | | | | D06412P | 3 | | | 050-099 |
| 003 | 22 | | PA | 73-6 | 33-51-11 | D10720 | | | | 3 | | | | D06412P | 3 | | | 150-199, 275-299 |
| 004 | 22 | | PA | 67-0 | 33-51-11 | D10720 | | | | 4 | | | | D06412P | 4 | | | 050-099 |
| 004 | 22 | | PA | 73-6 | 33-51-11 | D10720 | | | | 4 | | | | D06412P | 4 | | | 150-199, 275-299 |
| 005 | 22 | | PA | 2-0 | 33-51-11 | D10720 | | | | 5 | | | | D10720 | 6 | | | 050-099 |
| 005 | 22 | | PA | 0-7 | 33-51-11 | D10720 | | | | 5 | | | | D10720 | 6 | | | 150-199, 275-299 |
| 006 | 20 | | PA | 1-8 | 33-51-14 | D10720 | | | | 14 | | | | SM00014 | | S | | 275-299 |
| 007 | 20 | | PA | 3-0 | 33-51-11 | D10720 | | | | 7 | | | | GD04678 | S.. | E | | 050-099 |
| 007 | 20 | | PA | 2-7 | 33-51-11 | D10720 | | | | 7 | | | | GD04678 | S.. | E | | 150-199, 275-299 |
| 008 | 22 | | PA | 67-0 | 33-51-11 | D10720 | | | | 8 | | | | D06412P | 8 | | | 050-099 |
| 008 | 22 | | PA | 73-6 | 33-51-11 | D10720 | | | | 8 | | | | D06412P | 8 | | | 150-199, 275-299 |
| 009 | 18 | | PA | 34-0 | 33-51-14 | D10720 | | | | 9 | DK | | | L00322 | 1 | C | | 050-099, 150-199 |
| 009 | 16 | | PA | 34-0 | 33-51-14 | D10720 | | | | 9 | FM | | | L00322 | 1 | C | * | 275-299 |
| 010 | 18 | | PA | 25-0 | 33-51-14 | D10720 | | | | 10 | DK | | | L00297 | 1 | C | | 050-099 |
| 010 | 18 | | PA | 20-0 | 33-51-14 | D10720 | | | | 10 | DK | | | L00297 | 1 | C | | 150-199, 275-299 |
| 011 | 20 | | PA | 16-0 | 33-51-12 | D10720 | | | | 11 | | | | SM00009 | | S | | 050-099 |
| 011 | 18 | | PA | 19-6 | 33-51-14 | D10720 | | | | 11 | DK | | | L00699 | 1 | C | | 150-199, 275-299 |
| 012 | 20 | | PA | 29-0 | 33-51-12 | D10720 | | | | 12 | | | | L00296 | 1 | C | | 050-099 |
| 012 | 18 | | PA | 32-4 | 33-51-14 | D10720 | | | | 12 | DK | | | L00700 | 1 | C | | 150-199 |
| 012 | 16 | | PA | 32-4 | 33-51-14 | D10720 | | | | 12 | FM | | | L00700 | 1 | C | * | 275-299 |
| 014 | 20 | | PA | 16-0 | 33-51-12 | L00321 | | | | 1 | C | | | SM00009 | | S | | 050-099 |
| 017 | 20 | | PA | 2-9 | 33-51-16 | D11694 | | | | =1 | | | | GD04676 | D.. | E | | 275-299 |
| 020 | 22 | | PA | 2-0 | 33-51-14 | D10720 | | | | 20 | | | | D10720 | 24 | | | 050-099 |
| 020 | 22 | | PA | 0-7 | 33-51-14 | D10720 | | | | 20 | | | | D10720 | 24 | | | 150-199, 275-299 |
| 021 | 20 | | PA | 20-11 | 33-51-14 | L00322 | | | | 1 | C | * | | D11726 | =1 | | | 275-278 |
| 021 | 20 | | PA | 22-0 | 33-51-14 | L00322 | | | | 1 | C | * | | D11726 | =1 | | | 280-299 |
| 022 | 20 | | PA | 5-2 | 33-51-14 | D11728 | | | | =1 | | | | GD04652 | D.. | E | | 275-278 |
| 022 | 20 | | PA | 6-0 | 33-51-14 | D11728 | | | | =1 | | | | GD04652 | D.. | E | | 280-299 |
| 023 | 20 | | PA | 4-1 | 33-51-14 | SM00014 | | | | | S | | | D11730 | =1 | | | 275-299 |
| 024 | 20 | | PA | 4-9 | 33-51-14 | D11732 | | | | =1 | | | | GD04676 | D.. | E | | 275-299 |
| 026 | 18 | | PA | 4-0 | 33-51-14 | L00322 | | | | 2 | C | | | GD02546 | D.. | E | | 050-099, 280-299 |
| 026 | 18 | | PA | 3-1 | 33-51-14 | L00322 | | | | 2 | C | | | GD02546 | D.. | E | | 150-199, 275-278 |
| 027 | 18 | | PA | 4-0 | 33-51-14 | L00297 | | | | 2 | C | | | GD02498 | D.. | E | | 050-099, 280-299 |
| 027 | 18 | | PA | 2-11 | 33-51-14 | L00297 | | | | 2 | C | | | GD02498 | D.. | E | | 150-199, 275-278 |
| 028 | 18 | | PA | 2-5 | 33-51-14 | L00699 | | | | 2 | C | | | GD04632 | D.. | E | | 150-199, 275-299 |
| 030 | 18 | | PA | 2-10 | 33-51-14 | L00700 | | | | 2 | C | | | GD04636 | D.. | E | | 150-199, 275-299 |
| 031 | 20 | | PA | 23-2 | 33-51-14 | L00700 | | | | 1 | C | * | | D11734 | =1 | | | 275-299 |
| 032 | 20 | | PA | 4-2 | 33-51-14 | D11736 | | | | =1 | | | | GD04652 | D.. | E | | 275-278 |
| 032 | 20 | | PA | 5-0 | 33-51-14 | D11736 | | | | =1 | | | | GD04652 | D.. | E | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W0830

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0834 | 286T0834 | | | EMERGENCY LIGHTS (continued) | | | | | | | | | | | | |
| 033 | 20 | | PA | 3-10 | 33-51-14 | SM00014 | | | | | S | D11738 | = 1 | | | 275-299 |
| 034 | 20 | | PA | 3-11 | 33-51-14 | D11740 | = 1 | | | | | GD04676 | D.. | E | | 275-299 |
| 037 | 20 | | PA | 23-0 | 33-51-12 | D10720 | 13 | | | | | L00298 | 1 | C | | 050-099 |
| 037 | 20 | | PA | 3-4 | 33-51-16 | D10720 | 13 | | | | | D11692 | = 1 | | | 275-299 |
| 041 | 18 | | PA | 10-0 | 33-51-12 | L00321 | 2 | C | | | | GD01944 | D.. | 2 | | 050-099 |
| 043 | 20 | | PA | 10-0 | 33-51-12 | L00655 | 2 | C | | | | GD01944 | D.. | 2 | | 050-099 |
| 057 | 20 | | PA | 16-0 | 33-51-12 | L00655 | 1 | C | | | | SM00009 | | S | | 050-099 |
| 073 | 16 | | PA | 6-0 | 33-51-12 | L00298 | 2 | C | | | | GD01462 | D.. | E | | 050-099 |
| 074 | 20 | | PA | 6-0 | 33-51-12 | L00296 | 2 | C | | | | GD02496 | D.. | E | | 050-099 |
| 078 | 22 | | PA | 47-4 | 33-22-21 | D06412P | 7 | | | | | D06858J | = 1 | | | 162-199 |
| 079 | 20 | | PA | 14-2 | 33-22-21 | D06860P | = 1 | | | | | GD04968 | A.. | E | | 162-199 |
| W0836 | 286T0836 | | | EMERGENCY LIGHTS | | | | | | | | | | | | |
| 001 | 16 | | PA | 8-0 | 33-51-11 | D10722 | 1 | FM | | | | GD00054 | D.. | 2 | | 050-099 |
| 001 | 16 | | PA | 6-7 | 33-51-11 | D10722 | 1 | FM | | | | GD00054 | D.. | 2 | | 150-199 |
| 001 | 16 | | PA | 5-6 | 33-51-11 | D10722 | 1 | FM | | | | GD00054 | D.. | 2 | | 275-299 |
| 002 | 20 | | PA | 68-0 | 33-51-11 | D10722 | 2 | | | | | D06414P | 2 | | | 050-099 |
| 002 | 20 | | PA | 0-7 | 33-51-11 | D10722 | 2 | | | | | SM00008 | | S | | 150-199 |
| 002 | 20 | | PA | 79-0 | 33-51-11 | D10722 | 2 | | | | | D06414P | 2 | | | 275-299 |
| 003 | 22 | | PA | 38-0 | 33-51-11 | D10722 | 3 | | | | | SP02506 | | S | | 050-099 |
| 003 | 22 | | PA | 38-7 | 33-51-11 | SM00007 | | | | S | | SP02506 | | S | | 150-199 |
| 003 | 22 | | PA | 42-0 | 33-51-11 | D10722 | 3 | | | | | SP02506 | | S | | 275-299 |
| 004 | 22 | | PA | 68-0 | 33-51-11 | D10722 | 4 | | | | | D06414P | 4 | | | 050-099 |
| 004 | 22 | | PA | 0-7 | 33-51-11 | D10722 | 4 | | | | | SM00006 | | S | | 150-199 |
| 004 | 22 | | PA | 79-0 | 33-51-11 | D10722 | 4 | | | | | D06414P | 4 | | | 275-299 |
| 005 | 22 | | PA | 1-0 | 33-51-11 | D10722 | 5 | | | | | D10722 | 6 | | | 050-099, 275-299 |
| 005 | 22 | | PA | 0-7 | 33-51-11 | D10722 | 5 | | | | | D10722 | 6 | | | 150-199 |
| 007 | 20 | | PA | 7-0 | 33-51-11 | D10722 | 7 | | | | | GD00054 | S.. | 2 | | 050-099, 275-299 |
| 007 | 20 | | PA | 6-7 | 33-51-11 | D10722 | 7 | | | | | GD00054 | S.. | 2 | | 150-199 |
| 008 | 22 | | PA | 69-0 | 33-51-11 | D10722 | 8 | | | | | D06414P | 8 | | | 050-099 |
| 008 | 22 | | PA | 78-9 | 33-51-11 | D10722 | 8 | | | | | D06414P | 8 | | | 150-199 |
| 008 | 22 | | PA | 79-0 | 33-51-11 | D10722 | 8 | | | | | D06414P | 8 | | | 275-299 |
| 009 | 18 | | PA | 29-0 | 33-51-14 | D10722 | 9 | DK | | | | L00333 | 1 | C | | 050-099 |
| 009 | 18 | | PA | 28-4 | 33-51-14 | D10722 | 9 | DK | | | | L00333 | 1 | C | | 150-199 |
| 009 | 16 | | PA | 29-0 | 33-51-14 | D10722 | 9 | FM | | | | L00333 | 1 | C | * | 275-299 |
| 010 | 18 | | PA | 14-0 | 33-51-14 | D10722 | 10 | DK | | | | L00308 | 1 | C | | 050-099 |
| 010 | 18 | | PA | 12-9 | 33-51-14 | D10722 | 10 | DK | | | | L00308 | 1 | C | | 150-199 |
| 010 | 18 | | PA | 14-0 | 33-51-14 | D10722 | 10 | DK | | | | L00308 | 1 | C | * | 275-299 |
| 011 | 18 | | PA | 34-0 | 33-51-16 | D10722 | 13 | DK | | | | SM00003 | | S | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0830

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0836 | 286T0836 | | | EMERGENCY LIGHTS (continued) | | | | | | | | | | | | | |
| 012 | 20 | | PA | 15-0 | 33-51-16 | SM00003 | | | S | | | | D11700 | = 1 | | | 275-299 |
| 013 | 20 | | PA | 3-0 | 33-51-16 | D11702 | = 1 | | | | | | GD02708 | D.. | E | | 275-299 |
| 016 | 20 | | PA | 15-0 | 33-51-16 | SM00003 | | | S | | | | D11760 | 4 | | | 275-299 |
| 017 | 20 | | PA | 4-0 | 33-51-16 | D11760 | 7 | | | | | | GD02708 | D.. | E | | 275-299 |
| 018 | 20 | | PA | 4-0 | 33-51-16 | D11760 | 10 | | | | | | GD02710 | S.. | E | | 275-299 |
| 019 | 22 | | PA | 0-7 | 33-51-11 | D10722 | 3 | | | | | | SM00007 | | S | | 150-199 |
| 020 | 22 | | PA | 1-0 | 33-51-14 | D10722 | 20 | | | | | | D10722 | 24 | | | 050-099, 275-299 |
| 020 | 22 | | PA | 0-7 | 33-51-14 | D10722 | 20 | | | | | | D10722 | 24 | | | 150-199 |
| 021 | 20 | | PA | 10-0 | 33-51-14 | L00333 | 1 | C | | * | | | D11742 | = 1 | | | 275-299 |
| 022 | 20 | | PA | 4-0 | 33-51-14 | D11744 | = 1 | | | | | | GD04506 | D.. | 2 | | 275-299 |
| 023 | 20 | | PA | 10-0 | 33-51-14 | L00308 | 1 | C | | * | | | D11746 | = 1 | | | 275-299 |
| 024 | 20 | | PA | 4-0 | 33-51-14 | D11748 | = 1 | | | | | | GD00054 | D.. | 2 | | 275-299 |
| 026 | 18 | | PA | 6-0 | 33-51-14 | L00333 | 2 | C | | | | | GD00932 | D.. | 2 | | 050-099, 275-299 |
| 026 | 18 | | PA | 5-1 | 33-51-14 | L00333 | 2 | C | | | | | GD00932 | D.. | 2 | | 150-199 |
| 028 | 18 | | PA | 7-0 | 33-51-14 | L00308 | 2 | C | | | | | GD00070 | D.. | 2 | | 050-099, 275-299 |
| 028 | 18 | | PA | 6-4 | 33-51-14 | L00308 | 2 | C | | | | | GD00070 | D.. | 2 | | 150-199 |
| 029 | 20 | | PA | 78-9 | 33-51-11 | D06414P | 2 | | | | | | SM00008 | | S | | 150-199 |
| 030 | 22 | | PA | 78-9 | 33-51-11 | D06414P | 4 | | | | | | SM00006 | | S | | 150-199 |
| 038 | 20 | | PA | 24-0 | 33-51-12 | D10722 | 11 | | | | | | L00310 | 1 | C | | 050-099 |
| 039 | 20 | | PA | 14-0 | 33-51-12 | L00310 | 2 | C | | | | | GD00070 | D.. | 2 | | 050-099 |
| 040 | 20 | | PA | 25-0 | 33-51-12 | D10722 | 12 | | | | | | L01199 | 1 | C | | 050-099 |
| 041 | 16 | | PA | 15-0 | 33-51-12 | L01199 | 2 | | | | | | GD00070 | D.. | 2 | | 050-099 |
| 042 | 20 | | PA | 35-0 | 33-51-13 | D10722 | 13 | | | | | | L00422 | 1 | C | | 050-099 |
| 043 | 18 | | PA | 15-0 | 33-51-13 | L00422 | 2 | C | | | | | GD00932 | D.. | 2 | | 050-099 |
| 201B | 20 | | PB | AB | 34-0 | 33-51-16 | D11760 | 3 | | | | | SM00004 | | 9 | | 275-299 |
| 201R | 20 | | PB | AB | 0-0 | 33-51-16 | D11760 | 9 | | | | | SM00005 | | 9 | | 275-299 |
| 202B | 20 | | PB | IB | 20-0 | 33-51-16 | SM00004 | 9 | | | | | D06834J | = 1 | | | 275-299 |
| 202R | 20 | | PB | IB | 0-0 | 33-51-16 | SM00005 | 9 | | | | | D06836J | = 1 | | | 275-299 |
| 204B | 20 | | PB | ID | 23-0 | 33-51-16 | SM00004 | 9 | | | | | D06842J | = 1 | | | 275-299 |
| 204R | 20 | | PB | ID | 0-0 | 33-51-16 | SM00005 | 9 | | | | | D06844J | = 1 | | | 275-299 |
| 600 | 20 | | PA | 2-6 | 33-51-16 | D13246 | | C | | | | | D13234 | | A | | 150-199 |
| 601 | 20 | | PA | 2-6 | 33-51-16 | D13246 | | B | | | | | D13234 | | B | | 150-199 |
| 602 | 20 | | PA | 2-6 | 33-51-16 | D13246 | | F | | | | | D13234 | | C | | 150-199 |
| 603 | 20 | | PA | 2-6 | 33-51-16 | D13246 | | E | | | | | D13234 | | D | | 150-199 |
| 604 | 20 | | PA | 2-8 | 33-51-16 | D13246 | | D | | | | | GD05562 | D.. | E | | 150-199 |
| 605 | 22 | | PA | 70-10 | 33-51-16 | D13246 | | L | | | | | SM00006 | | S | | 150-199 |
| 606 | 22 | | PA | 70-10 | 33-51-16 | D13246 | | K | | | | | SM00007 | | S | | 150-199 |
| 607 | 20 | | PA | 70-10 | 33-51-16 | D13246 | | A | | | | | SM00008 | | S | | 150-199 |
| 901 | 16 | | PA | 3-0 | 33-51-14 | L09007 | 2 | C | | | | | GD00020 | D.. | 2 | | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W0830

Page 4

Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|--|----|---|----------|----------|---------|----|-----|-------|---------|---------|------|------|--------|-------|--------------|
| | | | | | Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term |
| W0836 | 286T0836 | | | EMERGENCY LIGHTS (continued) | | | | | | | | | | | | | |
| 911 | 16 | | PA | | 10-0 | 33-51-14 | D10722 | | 11 | FM | | L09007 | | 1 | C | | 150, 152-199 |
| A-A | | | | | 0-0 | 33-51-16 | D06834P | | =1 | | | L00984 | | =1 | | | 275-299 |
| A-B | | | | | 0-0 | 33-51-16 | D06836P | | =1 | | | L00984 | | =2 | | | 275-299 |
| A-E | | | | | 0-0 | 33-51-16 | D06842P | | =1 | | | L00986 | | =1 | | | 275-299 |
| A-F | | | | | 0-0 | 33-51-16 | D06844P | | =1 | | | L00986 | | =2 | | | 275-299 |
| W0838 | 286T0838 | | | RESERVE HYD SOURCE SELECT & INDICATION | | | | | | | | | | | | | |
| 001 | 18 | | UA | | 4-8 | 29-21-32 | D02212 | | 3 | | | D02214 | | 5 | | | ALL |
| 002 | 18 | | UA | | 11-3 | 29-21-32 | D05510P | | 2 | | | D02214 | | 3 | | | ALL |
| 003 | 20 | | UA | | 9-2 | 29-21-32 | D05510P | | 3 | | | D02212 | | 2 | | | ALL |
| 004 | 18 | | UA | | 11-3 | 29-21-32 | D05510P | | 4 | | | D02214 | | 1 | | | ALL |
| 005 | 20 | | UA | | 11-3 | 29-21-32 | D02214 | | 9 | | | D05510P | | 5 | | | ALL |
| 006 | 20 | | UA | | 9-2 | 29-21-32 | D05510P | | 6 | | | D02212 | | 1 | | | ALL |
| 007 | 18 | | UA | | 10-10 | 29-21-32 | D02214 | | 8 | | | SM00002 | | | 9 | | ALL |
| 008 | 18 | | UA | | 9-2 | 29-21-32 | D05510P | | 11 | | | D02212 | | 9 | | | ALL |
| 009 | 18 | | UA | | 4-8 | 29-21-32 | D02214 | | 2 | | | D02212 | | 4 | | | ALL |
| 010 | 20 | | UA | | 9-7 | 29-31-11 | D05510P | | 7 | | | D00554 | | 1 | | | ALL |
| 013 | 18 | | UA | | 8-9 | 29-21-32 | D02212 | | 10 | | | SM00001 | | | 9 | | ALL |
| 014 | 18 | | UA | | 10-10 | 29-21-32 | SM00001 | | | 9 | | D02214 | | 10 | | | ALL |
| 015 | 18 | | UA | | 1-0 | 29-21-32 | D05510P | | 10 | | | SM00001 | | | 9 | | ALL |
| 016 | 18 | | UA | | 8-9 | 29-21-32 | SM00002 | | | 9 | | D02212 | | 8 | | | ALL |
| 017 | 18 | | UA | | 1-0 | 29-21-32 | SM00002 | | | 9 | | D05510P | | 1 | | | ALL |
| 201B | 22 | | PB | AA | 9-7 | 29-31-11 | D00554 | | 3 | | | D05510P | | 9 | | | ALL |
| 201R | 22 | | PB | AA | 0-0 | 29-31-11 | D00554 | | 2 | | | D05510P | | 8 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0830

Page 5 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0840 | 286T0840 | | | LEFT MAIN GEAR UPPER J-BOX-SYS 1 | | | | | | | | | | | |
| 201B | 18 | | UB | B | 17-0 | 32-61-11 | D04302P | | | | D05026P | | | | 050-099 |
| 201B | 18 | | UB | B | 16-5 | 32-61-11 | D04302P | | | | D05026P | | | | 150-199, 275-299 |
| 201R | 18 | | UB | B | 0-0 | 32-61-11 | D04302P | | | | D05026P | | | | ALL |
| 202B | 18 | | UB | C | 17-0 | 32-61-11 | D04302P | | | | D05026P | | | | 050-099 |
| 202B | 18 | | UB | C | 16-5 | 32-61-11 | D04302P | | | | D05026P | | | | 150-199, 275-299 |
| 202R | 18 | | UB | C | 0-0 | 32-61-11 | D04302P | | | | D05026P | | | | ALL |
| 203B | 18 | | UB | A | 17-0 | 32-09-11 | D04302P | | | | D05026P | | | | 050-099 |
| 203B | 18 | | UB | A | 16-5 | 32-09-11 | D04302P | | | | D05026P | | | | 150-199, 275-299 |
| 203R | 18 | | UB | A | 0-0 | 32-09-11 | D04302P | | | | D05026P | | | | ALL |
| 204B | 20 | | VG | D | 17-0 | 32-42-11 | D04302P | | | | D05026P | | | | 050-099 |
| 204B | 20 | | VG | D | 16-5 | 32-42-11 | D04302P | | | | D05026P | | | | 150-199, 275-299 |
| 204R | 20 | | VG | D | 0-0 | 32-42-11 | D04302P | | | | D05026P | | | | ALL |
| 204Z | | | | D | 0-0 | 32-42-11 | D04302P | | | | D05026P | | | | ALL |
| 205B | 20 | | VG | E | 17-0 | 32-42-11 | D04302P | | | | D05026P | | | | 050-099 |
| 205B | 20 | | VG | E | 16-5 | 32-42-11 | D04302P | | | | D05026P | | | | 150-199, 275-299 |
| 205R | 20 | | VG | E | 0-0 | 32-42-11 | D04302P | | | | D05026P | | | | ALL |
| 205Z | | | | E | 0-0 | 32-42-11 | D04302P | | | | D05026P | | | | ALL |
| 207B | 20 | | VG | K | 20-0 | 32-45-13 | D06340P | | | | D05026P | | | | 050-099 |
| 207B | 20 | | VG | K | 19-4 | 32-45-13 | D06340P | | | | D05026P | CAP | Y | | 150-154 |
| 207B | 20 | | VG | K | 19-4 | 32-45-13 | D06340P | | | | D05026P | | | | 155-199, 275-299 |
| 207R | 20 | | VG | K | 0-0 | 32-45-13 | D06340P | | | | D05026P | | | | 050-099, 155-199, 275-299 |
| 207R | 20 | | VG | K | 0-0 | 32-45-13 | D06340P | | | | D05026P | CAP | Y | | 150-154 |
| 207Z | | | | K | 0-0 | 32-45-13 | D06340P | | | | D05026P | | | | 050-099, 155-199, 277-299 |
| 207Z | | | | K | 0-0 | 32-45-13 | D06340P | | | | D05026P | DED | | | 150-154, 275-276 |
| 208B | 20 | | VG | L | 20-0 | 32-45-13 | D06340P | | | | D05026P | | | | 050-099 |
| 208B | 20 | | VG | L | 19-4 | 32-45-13 | D06340P | | | | D05026P | CAP | Y | | 150-154 |
| 208B | 20 | | VG | L | 19-4 | 32-45-13 | D06340P | | | | D05026P | | | | 155-199, 275-299 |
| 208R | 20 | | VG | L | 0-0 | 32-45-13 | D06340P | | | | D05026P | | | | 050-099, 155-199, 275-299 |
| 208R | 20 | | VG | L | 0-0 | 32-45-13 | D06340P | | | | D05026P | CAP | Y | | 150-154 |
| 208Z | | | | L | 0-0 | 32-45-13 | D06340P | | | | D05026P | | | | 050-099, 155-199, 277-299 |
| 208Z | | | | L | 0-0 | 32-45-13 | D06340P | | | | D05026P | DED | | | 150-154, 275-276 |
| 451G | 18 | | UY | F | 17-0 | 32-46-11 | D04302P | | 4G | | D05026P | | 8 | 4H | 050-099 |
| 451G | 18 | | UY | F | 16-5 | 32-46-11 | D04302P | | 4G | | D05026P | | 8 | 4H | 150-199, 275-299 |
| 451W | 18 | | UY | F | 0-0 | 32-46-11 | D04302P | | 4K | | D05026P | | 7 | 4L | ALL |
| 452G | 18 | | UY | G | 17-0 | 32-46-11 | D04302P | | 4G | | D05026P | | 10 | 4H | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0840

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0840 | 286T0840 | | | LEFT MAIN GEAR UPPER J-BOX-SYS 1 (continued) | | | | | | | | | | | | |
| 452G | 18 | UY | G | 16-5 | 32-46-11 | D04302P | 15 | 4G | | D05026P | 10 | 4H | | 150-199, 275-299 | | |
| 452W | 18 | UY | G | 0-0 | 32-46-11 | D04302P | 14 | 4K | | D05026P | 9 | 4L | | ALL | | |
| W0842 | 286T0842 | | | FWD L DOOR VIEWPORT HEATER. | | | | | | | | | | | | |
| 001 | 20 | 8R | | 7-0 | 30-46-11 | D06604J | | 1 | | SP03280 | | 9 | | ALL | | |
| 002 | 20 | 8R | | 7-0 | 30-46-11 | D06604J | | 2 | | SP03282 | | 9 | | ALL | | |
| 003 | 20 | 8R | | 6-0 | 30-46-11 | D06604J | | 3 | | GD05452 | S.. | E | | ALL | | |
| A-A | | | | 0-0 | 30-46-11 | B00283 | | = P | | SP03280 | | 9 | | ALL | | |
| A-B | | | | 0-0 | 30-46-11 | B00283 | | = G | | SP03282 | | 9 | | ALL | | |
| W0843 | 286T0843 | | | VHF-L, SHELF TO CONTROL PANEL | | | | | | | | | | | | |
| 001 | 18 | PA | | 4-0 | 33-13-18 | SP02276 | | | 9 | D00407 | 1 | DK | | 050-099, 150-155, 162-165, 275-276 | | |
| 002 | 18 | PA | | 2-1 | 33-13-18 | GD04452 | A.. | 2 | | D00407 | 2 | DK | | 050-099, 150-155, 162-165, 275-276 | | |
| 004 | 18 | PA | | 33-0 | 23-12-11 | D04927J | | 4 | | D00407 | 13 | DK | | ALL | | |
| 014 | 20 | PA | | 2-1 | 23-12-11 | GD04454 | D.. | 2 | | D00407 | 14 | | | 050-099, 150-199, 275-276 | | |
| 014 | 20 | PA | | 2-1 | 23-12-11 | GD04474 | D.. | 2 | | D00407 | 14 | | | 277-299 | | |
| 201B | 24 | PW | IA | 33-0 | 23-12-11 | D04927J | | 7 | | D00407 | 18 | | | ALL | | |
| 201R | 24 | PW | IA | 0-0 | 23-12-11 | D04927J | | 6 | | D00407 | 17 | | | ALL | | |
| 201Z | | | IA | 0-0 | 23-12-11 | D04927J | | 10 | | D00407 | 19 | | | ALL | | |
| 204B | 18 | PB | ID | 4-0 | 33-13-18 | SP05000 | | | 9 | D00407 | 2 | DK | | 156-157, 166-199, 277-299 | | |
| 204R | 18 | PB | ID | 0-0 | 33-13-18 | SP02276 | | | 9 | D00407 | 1 | DK | | 156-157, 166-199, 277-299 | | |
| 401B | 24 | PY | QA | 33-0 | 23-42-11 | D00849 | | 3 | \$D | D04927J | 3 | | | ALL | | |
| 401G | 24 | PY | QA | 0-0 | 23-42-11 | D00849 | | 5 | \$D | D04927J | 5 | | | ALL | | |
| 401R | 24 | PY | QA | 0-0 | 23-42-11 | D00849 | | 1 | \$D | D04927J | 1 | | | ALL | | |
| 401Y | 24 | PY | QA | 0-0 | 23-42-11 | D00849 | | 4 | \$D | D04927J | 11 | | | ALL | | |
| 401Z | | | QA | 0-0 | 23-42-11 | D00849 | | 2 | \$D | D04927J | 2 | | | ALL | | |
| 900 | 20 | PA | | 2-1 | 23-12-11 | GD04454 | D.. | 2 | | D00407 | 4 | | | 150, 152-199, 275-299 | | |
| W0844 | 286T0844 | | | FWD R DOOR VIEWPORT HEATER. | | | | | | | | | | | | |
| 001 | 20 | 8R | | 7-0 | 30-46-11 | D06606J | | 1 | | SP03284 | | 9 | | ALL | | |
| 002 | 20 | 8R | | 7-0 | 30-46-11 | D06606J | | 2 | | SP03286 | | 9 | | ALL | | |
| 003 | 20 | 8R | | 6-0 | 30-46-11 | D06606J | | 3 | | GD05454 | S.. | E | | ALL | | |
| A-A | | | | 0-0 | 30-46-11 | B00284 | | = P | | SP03284 | | 9 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0840

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|---------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0844 | 286T0844 | | | FWD R DOOR VIEWPORT HEATER. (continued) | | | | | | | | | | | |
| A-B | | | | | 0-0 | 30-46-11 | B00284 | = | G | | SP03286 | | 9 | | ALL |
| W0845 | 286T0845 | | | VHF-R, SHELF TO CONTROL PANEL | | | | | | | | | | | |
| 001 | 18 | | PA | | 13-0 | 33-13-18 | SP02286 | | | 9 | D00409 | 1 | DK | | 050-099, 150-155, 162-165, 275-276 |
| 002 | 18 | | PA | | 1-8 | 33-13-18 | GD04456 | A.. | | 2 | D00409 | 2 | DK | | 050-099, 150-155, 162-165, 275-276 |
| 004 | 18 | | PA | | 26-0 | 23-12-21 | D04929J | | | 4 | D00409 | 13 | DK | | ALL |
| 005 | 24 | | PK | | 30-0 | 23-51-11 | D04929J | | | 12 | SP00481 | | W | | 050-099, 151-199, 275-299 |
| 005 | 24 | | PK | | 30-0 | 23-51-11 | D04929J | | | 12 | SP00901 | | W | | 150 |
| 006 | 24 | | PK | | 30-0 | 23-51-11 | D04929J | | | 8 | SP00507 | | W | | 050-099, 151-199, 275-299 |
| 006 | 24 | | PK | | 30-0 | 23-51-11 | D04929J | | | 8 | SP00903 | | W | | 150 |
| 014 | 20 | | PA | | 1-11 | 23-12-21 | GD04454 | D.. | | 2 | D00409 | 14 | | | 050-099, 150-199, 275-276 |
| 014 | 20 | | PA | | 1-11 | 23-12-21 | GD04474 | D.. | | 2 | D00409 | 14 | | | 277-299 |
| 201B | 24 | | PW | IA | 26-0 | 23-12-21 | D04929J | | | 2 | D00409 | 18 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 23-12-21 | D04929J | | | 1 | D00409 | 17 | | | ALL |
| 201Z | | | | IA | 0-0 | 23-12-21 | D04929J | | | 3 | D00409 | 19 | | | ALL |
| 203B | 18 | | PB | IC | 13-0 | 33-13-18 | SP05010 | | | 9 | D00409 | 2 | DK | | 156-157, 166-199, 277-299 |
| 203R | 18 | | PB | IC | 0-0 | 33-13-18 | SP02286 | | | 9 | D00409 | 1 | DK | | 156-157, 166-199, 277-299 |
| 900 | 20 | | PA | | 2-9 | 23-12-21 | GD04454 | D.. | | 2 | D00409 | 4 | | | 150, 152-199, 275-299 |
| W0847 | 286T0847 | | | VHF-C, SHELF TO CONTROL PANEL | | | | | | | | | | | |
| 001 | 18 | | PA | | 2-0 | 33-13-18 | D00411 | | | 1 | DK | SP02270 | | 9 | 050-099, 150-155, 162-165, 275-276 |
| 002 | 18 | | PA | | 1-9 | 33-13-18 | D00411 | | | 2 | DK | GD04474 | A.. | 2 | 050-099, 150-155, 162-165, 275-276 |
| 003 | 24 | | PK | | 31-0 | 23-22-12 | D00411 | | | 16 | | D04931J | CAP | Y | 167-199 |
| 004 | 18 | | PA | | 31-0 | 23-12-31 | D00411 | | | 13 | DK | D04931J | | 4 | ALL |
| 005 | 24 | | PK | | 31-0 | 23-22-12 | D00411 | | | 15 | | D04931J | CAP | Y | 167-199 |
| 014 | 20 | | PA | | 1-9 | 23-12-31 | D00411 | | | 14 | | GD04474 | D.. | 2 | ALL |
| 016 | 22 | | PA | | 11-0 | SPARE | TB0031H | | | 8 | 2 | D00411 | CAP | Y | 167-199 |
| 017 | 22 | | PA | | 11-0 | SPARE | TB0031H | | | 6 | 2 | D00411 | CAP | Y | 167-199 |
| 201B | 24 | | PW | IA | 31-0 | 23-12-31 | D00411 | | | 18 | | D04931J | | 7 | ALL |
| 201R | 24 | | PW | IA | 0-0 | 23-12-31 | D00411 | | | 17 | | D04931J | | 6 | ALL |

WIRE LIST

D280T132

91-21-11
Section W0840
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|----|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W0847 | 286T0847 | | | VHF-C, SHELF TO CONTROL PANEL (continued) | | | | | | | | | | | | | | |
| 201Z | | | IA | 0-0 | 23-12-31 | D00411 | | 19 | | | | | D04931J | | 10 | | | ALL |
| 203B | 18 | | PB IC | 3-0 | 33-13-18 | D00411 | | 1 | DK | | | | SP02270 | | 9 | | | 156-157, 166-199 |
| 203B | 18 | | PB IC | 3-0 | 33-13-18 | D00411 | | 2 | DK | | | | SP04096 | | 9 | | | 277-299 |
| 203R | 18 | | PB IC | 0-0 | 33-13-18 | D00411 | | 2 | DK | | | | SP04096 | | 9 | | | 156-157, 166-199 |
| 203R | 18 | | PB IC | 0-0 | 33-13-18 | D00411 | | 1 | DK | | | | SP02270 | | 9 | | | 277-299 |
| 214B | 24 | | PW IN | 33-0 | 23-22-12 | D04931J | | 2 | | | | | TB0255Y | C003 | BJ | | | ALL |
| 214R | 24 | | PW IN | 0-0 | 23-22-12 | D04931J | | 1 | | | | | TB0255Y | A003 | BJ | | | ALL |
| 214Z | | | IN | 0-0 | 23-22-12 | D04931J | | 3 | | | | | TB0255Y | A004 | BJ | | | ALL |
| 900 | 20 | | PA | 2-9 | 23-12-31 | GD04454 | | D.. | 2 | | | | D00411 | | 4 | | | 150, 152-199, 275-299 |
| W0849 | 286T0849 | | | E2-5 SHELF TO F/E PNL | | | | | | | | | | | | | | |
| 001 | 22 | | PA | 29-0 | SPARE | D04953J | | 1 | | | | | D04955P | | 1 | | | 050-099 |
| 001 | 22 | | PA | 29-0 | SPARE | D04953J | | 1 | | | | | D04955P | | 6 | | | 150-154 |
| 004 | 24 | | PV AD | 17-0 | 23-51-41 | SP00337 | | | | VL | | | D04955P | | 4 | | | ALL |
| 004Z | | | AD | 0-0 | 23-51-41 | SP00337 | | | REF | | | 37 | D04955P | | 5 | | | ALL |
| 008 | 24 | | PK | 29-0 | SPARE | D04953J | | 11 | | | | | D04955P | | 11 | | | ALL |
| 010 | 22 | | PA | 29-0 | SPARE | D04953J | | 13 | | | | | D04955P | | 13 | | | ALL |
| 014 | 24 | | PK | 29-0 | 23-51-41 | D04955P | | 3 | | | | | D04953J | | 3 | | | ALL |
| 015 | 24 | | PK | 29-0 | 23-22-15 | D04955P | | 8 | | | | | D04953J | | 8 | | | 050-099, 155-199, 275-299 |
| 015 | 24 | | PK | 35-0 | 23-22-15 | D04955P | | 8 | | | | | D04953J | | 8 | | | 150-154 |
| 202 | 20 | | UA | 4-0 | 23-41-11 | D04953J | | | | | | FB | GD00019 | S.. | E | | | ALL |
| 202B | 24 | | PW IB | 29-0 | 23-41-11 | D04953J | | 15 | | | | | D04955P | | 15 | | | ALL |
| 202R | 24 | | PW IB | 0-0 | 23-41-11 | D04953J | | 14 | | | | | D04955P | | 14 | | | ALL |
| 202Z | | | IB | 0-0 | 23-41-11 | D04953J | | | | | | FB | D04955P | | | | FA | ALL |
| 203B | 24 | | PW IC | 29-0 | 23-41-11 | D04953J | | 17 | | | | | D04955P | | 17 | | | ALL |
| 203R | 24 | | PW IC | 0-0 | 23-41-11 | D04953J | | 16 | | | | | D04955P | | 16 | | | ALL |
| 203Z | | | IC | 0-0 | 23-41-11 | D04953J | | | | | | FB | D04955P | | | | FA | ALL |
| 204B | 24 | | PW ID | 29-0 | 23-22-15 | D04955P | | 7 | | | | | D04953J | | 7 | | | 050-099, 155-199, 275-299 |
| 204B | 24 | | PW ID | 35-0 | 23-22-15 | D04955P | | 7 | | | | | D04953J | | 7 | | | 150-154 |
| 204R | 24 | | PW ID | 0-0 | 23-22-15 | D04955P | | 6 | | | | | D04953J | | 6 | | | 050-099, 155-199, 275-299 |
| 204R | 24 | | PW ID | 0-0 | 23-22-15 | D04955P | | 10 | | | | | D04953J | | 6 | | | 150-154 |
| 204Z | | | ID | 0-0 | 23-22-15 | D04955P | | 9 | | | | | D04953J | | 9 | | | ALL |
| FRA | | | | 0-0 | 23-41-11 | D04955P | | 21 | | | | | D04955P | | | | FA | ALL |

WIRE LIST

D280T132

91-21-11

Section W0840

Page 4 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0850 | 286T0850 | | | AFT L DOOR VIEWPORT HEATER. | | | | | | | | | | | |
| 001 | 20 | | 8R | | 7-0 | 30-46-11 | D06612J | | | | SP03296 | | 9 | | ALL |
| 002 | 20 | | 8R | | 7-0 | 30-46-11 | D06612J | | | | SP03298 | | 9 | | ALL |
| 003 | 20 | | 8R | | 6-0 | 30-46-11 | D06612J | | | | GD05460 | S.. | E | | ALL |
| A-A | | | | | 0-0 | 30-46-11 | B00285 | | =P | | SP03296 | | 9 | | ALL |
| A-B | | | | | 0-0 | 30-46-11 | B00285 | | =G | | SP03298 | | 9 | | ALL |
| W0851 | 286T0851 | | | ACARS CONTROL UNIT TO SHELF | | | | | | | | | | | |
| 025 | 22 | | PA | | 26-0 | 23-22-12 | D04953J | 22 | | | D02891 | | 6 | | 275-276, 280-299 |
| 025 | 22 | | PA | | 26-0 | 23-22-12 | D04957J | 53 | | | D02891 | | 6 | | 277-278 |
| 026 | 22 | | PA | | 26-0 | 23-22-12 | D04953J | 23 | | | D02891 | | 8 | | 275-276, 280-299 |
| 026 | 22 | | PA | | 26-0 | 23-22-12 | D04957J | 54 | | | D02891 | | 8 | | 277-278 |
| 043 | 22 | | PA | | 26-0 | 23-22-12 | D04953J | 24 | | | D02891 | | 9 | | 275-276, 280-299 |
| 043 | 22 | | PA | | 26-0 | 23-22-12 | D04957J | 55 | | | D02891 | | 9 | | 277-278 |
| 044 | 20 | | PA | | 4-0 | 23-22-12 | D02891 | 7 | | | GD04472 | D.. | 2 | | 275-299 |
| 045 | 22 | | PA | | 13-0 | 33-16-18 | D02891 | 4 | | | TB0031H | | 6 | 2 | 275-299 |
| 046 | 22 | | PA | | 13-0 | 33-16-18 | D02891 | 3 | | | TB0031H | | 8 | 2 | 275-299 |
| 214B | 20 | | PB | IN | 6-0 | 33-13-18 | D02891 | 2 | | | SP05004 | | 9 | | 275-299 |
| 214R | 20 | | PB | IN | 0-0 | 33-13-18 | D02891 | 1 | | | SP02280 | | 9 | | 275-299 |
| 901 | 22 | | PA | | 20-0 | 23-22-12 | D09090 | 3 | | | TB0031H | | 8 | 2 | 150, 152-199 |
| 902 | 22 | | PA | | 20-0 | 23-22-12 | D09090 | 5 | | | GD04472 | D.. | E | | 150, 152-199 |
| 903 | 22 | | PA | | 20-0 | 23-22-12 | D09090 | 4 | | | D04931J | | 12 | | 150, 152-199 |
| 904 | 22 | | PA | | 20-0 | 23-22-12 | D09090 | 6 | | | D04931J | | 5 | | 150, 152-199 |
| 905 | 20 | | PQ | AC | 20-0 | 23-22-12 | D09090 | 7 | | | D04931J | | 11 | | 150, 152-199 |
| 905Z | | | | AC | 0-0 | 23-22-12 | D09090 | DED | | | D04931J | DED | | | 150, 152-199 |
| 906 | 22 | | PA | | 20-0 | 23-22-12 | D09090 | 8 | | | TB0031H | | 6 | 2 | 150, 152-199 |
| 907B | 20 | | PB | AD | 0-0 | 23-22-12 | D09090 | 2 | | | GD04452 | A.. | E | | 150, 152-155, 162-165 |
| 907B | 20 | | PB | AD | 0-0 | 23-22-12 | D09090 | 2 | | | SP05004 | | 9 | | 156-157, 166-199 |
| 907R | 20 | | PB | AD | 20-0 | 23-22-12 | D09090 | 1 | | | SP02280 | | 9 | | 150, 152-199 |
| W0852 | 286T0852 | | | AFT R DOOR VIEWPORT HEATER. | | | | | | | | | | | |
| 001 | 20 | | 8R | | 7-0 | 30-46-11 | D06614J | | | | SP03300 | | 9 | | ALL |
| 002 | 20 | | 8R | | 7-0 | 30-46-11 | D06614J | | | | SP03302 | | 9 | | ALL |
| 003 | 20 | | 8R | | 6-0 | 30-46-11 | D06614J | | | | GD05462 | S.. | E | | ALL |
| A-A | | | | | 0-0 | 30-46-11 | B00286 | | =P | | SP03300 | | 9 | | ALL |
| A-B | | | | | 0-0 | 30-46-11 | B00286 | | =G | | SP03302 | | 9 | | ALL |
| W0853 | 286T0853 | | | E2-5 TO P37 & P33 | | | | | | | | | | | |
| 003 | 24 | | PK | | 20-0 | 23-31-13 | D05541P | 3 | | | D04963J | | 3 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0850
Page 1
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0853 | 286T0853 | | | E2-5 TO P37 & P33 (continued) | | | | | | | | | | | |
| 004 | 22 | | PA | | 20-0 | SPARE | D05541P | | 4 | | D04963J | | 4 | | ALL |
| 005 | 16 | | PA | | 15-5 | 23-34-11 | D05541P | | 15 | | D05195P | | 14 | | 050-099 |
| 005 | 16 | | PA | | 13-0 | 23-34-11 | D05541P | | 5 | FL | D05195P | | 1 | FM | 150-199 |
| 005 | 16 | | PA | | 13-0 | 23-34-11 | D05541P | | 15 | | D05195P | | 14 | | 275-278 |
| 005 | 16 | | PA | | 13-0 | 23-34-11 | D05541P | | 15 | | D05195P | | 1 | FM | 280-299 |
| 006 | 16 | | PA | | 15-5 | 23-34-11 | D05541P | | 19 | | D05195P | | 16 | | 050-099 |
| 006 | 16 | | PA | | 13-0 | 23-34-11 | D05541P | | 6 | FL | D05195P | | 2 | FM | 150-199 |
| 006 | 16 | | PA | | 13-0 | 23-34-11 | D05541P | | 19 | | D05195P | | 16 | | 275-299 |
| 007 | 16 | | PA | | 22-0 | 23-34-11 | SP00257 | | | S | D05195P | | 24 | | 050-099 |
| 007 | 16 | | PA | | 22-0 | 23-34-11 | SP00257 | | | 9 | D05195P | | 3 | FM | 150-199 |
| 007 | 16 | | PA | | 22-0 | 23-34-11 | SP00257 | | | 9 | D05195P | | 24 | | 275-299 |
| 008 | 16 | | PA | | 22-0 | 23-34-11 | SP00259 | | | S | D05195P | | 22 | | 050-099 |
| 008 | 16 | | PA | | 22-0 | 23-34-11 | SP00259 | | | 9 | D05195P | | 4 | FM | 150-199 |
| 008 | 16 | | PA | | 22-0 | 23-34-11 | SP00259 | | | 9 | D05195P | | 22 | | 275-299 |
| 009 | 22 | | PA | | 29-0 | SPARE | D04963J | | 7 | | D05195P | | 5 | | ALL |
| 012 | 12 | | PA | | 22-0 | 23-34-17 | SP00141 | | | S | D05195P | | 18 | | 050-099 |
| 012 | 12 | | PA | | 22-0 | 23-34-17 | SP00141 | | | 9 | D05195P | | 18 | | 150-199, 275-299 |
| 013 | 20 | | PA | | 15-5 | SPARE | D05541P | | 12 | | D05195P | | 12 | | 050-099 |
| 013 | 20 | | PA | | 13-0 | SPARE | D05541P | | 12 | | D05195P | | 12 | | 150-199, 275-299 |
| 014 | 10 | | PA | | 22-0 | 23-34-19 | SP00055 | | | S | D05195P | | 20 | EO | 050-099 |
| 014 | 10 | | PA | | 22-0 | 23-34-19 | SP00055 | | | 9 | D05195P | | 20 | EO | 150-199, 275-299 |
| 015 | 24 | | PK | | 20-0 | SPARE | D05541P | | 7 | | D04963J | | 8 | | ALL |
| 016 | 20 | | PA | | 29-0 | SPARE | D05195P | | 10 | | D04963J | | 10 | | ALL |
| 019 | 22 | | PA | | 29-0 | 23-34-11 | D05195P | | 8 | | D04963J | | 5 | | ALL |
| 020 | 24 | | PK | | 20-0 | 23-12-21 | D05541P | | 11 | | D04963J | | 11 | | ALL |
| 021 | 20 | | PA | | 4-0 | 23-34-11 | D04963J | | 6 | | GD00529 | | A.. | E | ALL |
| 031 | 12 | | PA | | 22-0 | 23-34-17 | SP00561 | | | 9 | D05195P | | 14 | | 280-299 |
| W0855 | 286T0855 | | | ADC-R AND FMC-R,SHELF TO F/O INSTR PNL | | | | | | | | | | | |
| 001 | 24 | | PK | | 53-0 | SPARE | D04965J | | 51 | | D04967J | | 1 | | 050-099 |
| 001 | 24 | | PK | | 54-0 | SPARE | D04965J | | 51 | | D04967J | | 1 | | 150-199, 275-299 |
| 002 | 22 | | PA | | 53-0 | SPARE | D04965J | | 42 | | D04967J | | 2 | | 050-099 |
| 002 | 22 | | PA | | 54-0 | SPARE | D04965J | | 42 | | D04967J | | 2 | | 150-199, 275-299 |
| 003 | 24 | | PK | | 53-0 | SPARE | D04965J | | 43 | | D04967J | | 3 | | 050-099 |
| 003 | 24 | | PK | | 54-0 | SPARE | D04965J | | 43 | | D04967J | | 3 | | 150-199, 275-299 |
| 004 | 24 | | PK | | 53-0 | SPARE | D04965J | | 44 | | D04967J | | 4 | | 050-099 |
| 004 | 24 | | PK | | 54-0 | SPARE | D04965J | | 44 | | D04967J | | 4 | | 150-199, 275-299 |
| 005 | 24 | | PK | | 53-0 | SPARE | D04965J | | 45 | | D04967J | | 5 | | 050-099 |
| 005 | 24 | | PK | | 54-0 | SPARE | D04965J | | 45 | | D04967J | | 5 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0850

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|----|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0855 | 286T0855 | | | ADC-R AND FMC-R,SHELF TO F/O INSTR PNL (continued) | | | | | | | | | | | | | | |
| 007 | 24 | | PK | | 25-0 | 31-31-19 | D04505J | | 51 | | | | D04965J | | 46 | | | ALL |
| 014 | 22 | | PA | | 27-0 | 34-12-62 | D04965J | | 19 | | | | D04505J | | 19 | | | ALL |
| 015 | 22 | | PA | | 27-0 | 34-12-62 | D04965J | | 20 | | | | D04505J | | 20 | | | ALL |
| 028 | 22 | | PA | | 25-0 | 34-12-62 | D04505J | | 28 | | | | D04965J | | 28 | | | ALL |
| 029 | 22 | | PA | | 25-0 | 34-61-26 | D04965J | | 29 | | | | D04505J | | 29 | | | 050-099 |
| 029 | 24 | | PK | | 25-0 | 34-61-26 | D04505J | | 29 | | | | D04965J | | 29 | | | 150-199 |
| 029 | 24 | | PK | | 25-0 | 34-61-26 | D04965J | | 29 | | | | D04505J | | 29 | | | 275-299 |
| 030 | 22 | | PA | | 25-0 | 34-61-24 | D04965J | | 30 | | | | D04505J | | 30 | | | ALL |
| 031 | 24 | | PK | | 25-0 | 34-12-22 | D04505J | | 31 | | | | D04965J | | 31 | | | ALL |
| 032 | 22 | | PA | | 25-0 | 34-61-21 | D04505J | | 32 | | | | D04965J | | 32 | | | ALL |
| 034 | 24 | | PK | | 25-0 | 32-42-11 | D04965J | | 27 | | | | D04505J | | 27 | | | ALL |
| 035 | 24 | | PK | | 25-0 | 31-31-19 | D04505J | | 52 | | | | D04965J | | 47 | | | ALL |
| 039 | 24 | | PK | | 25-0 | 34-61-26 | D04505J | | 39 | | | | D04965J | | 39 | | | ALL |
| 055 | 24 | | PK | | 25-0 | 31-31-18 | D04965J | | 25 | | | | D04505J | | 45 | | | 050-099 |
| 055 | 24 | | PK | | 25-0 | 31-31-18 | D04505J | | 45 | | | | D04965J | | 25 | | | 150-199, 275-299 |
| 057 | 24 | | PK | | 25-0 | 31-31-18 | D04965J | | 2 | | | | D04505J | | 47 | | | 050-099 |
| 057 | 24 | | PK | | 25-0 | 31-31-18 | D04505J | | 47 | | | | D04965J | | 2 | | | 150-199, 275-299 |
| 059 | 22 | | PA | | 25-0 | 31-31-18 | D04965J | | 52 | | | | D04505J | | 49 | | | 050-099 |
| 059 | 22 | | PA | | 25-0 | 31-31-18 | D04505J | | 49 | | | | D04965J | | 52 | | | 150-199, 275-299 |
| 060 | 24 | | PK | | 25-0 | 31-31-18 | D04965J | | 40 | | | | D04505J | | 50 | | | 050-099 |
| 060 | 24 | | PK | | 25-0 | 31-31-18 | D04505J | | 50 | | | | D04965J | | 40 | | | 150-199, 275-299 |
| 063 | 24 | | PK | | 25-0 | 31-31-18 | D04965J | | 3 | | | | D04505J | | 43 | | | 050-099 |
| 063 | 24 | | PK | | 25-0 | 31-31-18 | D04505J | | 43 | | | | D04965J | | 3 | | | 150-199, 275-299 |
| 064 | 24 | | PK | | 25-0 | 31-31-18 | D04965J | | 24 | | | | D04505J | | 44 | | | 050-099 |
| 064 | 24 | | PK | | 25-0 | 31-31-18 | D04505J | | 44 | | | | D04965J | | 24 | | | 150-199, 275-299 |
| 065 | 24 | | PK | | 25-0 | 31-31-18 | D04965J | | 1 | | | | D04505J | | 55 | | | 050-099 |
| 065 | 24 | | PK | | 25-0 | 31-31-18 | D04505J | | 55 | | | | D04965J | | 1 | | | 150-199, 275-299 |
| 066 | 24 | | PK | | 25-0 | 31-31-18 | D04965J | | 26 | | | | D04505J | | 46 | | | 050-099 |
| 066 | 24 | | PK | | 25-0 | 31-31-18 | D04505J | | 46 | | | | D04965J | | 26 | | | 150-199, 275-299 |
| 078 | 24 | | PK | | 25-0 | 31-31-18 | D04965J | | 41 | | | | D04505J | | 48 | | | 050-099 |
| 078 | 24 | | PK | | 25-0 | 31-31-18 | D04505J | | 48 | | | | D04965J | | 41 | | | 150-199, 275-299 |
| 201B | 22 | | PB | IA | 25-0 | 34-12-21 | D04505J | | 5 | | | | D04965J | | 5 | | | ALL |
| 201R | 22 | | PB | IA | 0-0 | 34-12-21 | D04505J | | 4 | | | | D04965J | | 4 | | | ALL |
| 202 | 20 | | UA | | 1-6 | 34-13-21 | GD00553 | | S.. | 2 | | | D04965J | | | | IB | ALL |
| 202B | 24 | | PW | IB | 25-0 | 34-13-21 | D04505J | | 10 | | | | D04965J | | 10 | | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-13-21 | D04505J | | 9 | | | | D04965J | | 9 | | | ALL |
| 202Z | | | | IB | 0-0 | 34-13-21 | D04505J | | 11 | | | | D04965J | | | | IB | ALL |
| 203 | 20 | | UA | | 1-6 | SPARE | D04965J | | | | IC | | GD00553 | | S.. | 2 | | 150-154, 275-299 |
| 203B | 24 | | PW | IC | 25-0 | SPARE | D04505J | | 22 | | | | D04965J | | 22 | | | 150-154, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0850
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0855 | 286T0855 | | | ADC-R AND FMC-R,SHELF TO F/O INSTR PNL (continued) | | | | | | | | | | | |
| 203R | 24 | PW | IC | | 0-0 | SPARE | D04505J | 21 | | | D04965J | 21 | | | 150-154, 275-299 |
| 203Z | | | IC | | 0-0 | SPARE | D04505J | 23 | | | D04965J | | | IC | 150-154, 275-299 |
| 204 | 20 | UA | | | 1-6 | 34-61-24 | D04965J | | | ID | GD00553 | S.. | 2 | | ALL |
| 204B | 24 | PW | ID | | 25-0 | 34-61-24 | D04505J | 13 | | | D04965J | 13 | | | ALL |
| 204R | 24 | PW | ID | | 0-0 | 34-61-24 | D04505J | 12 | | | D04965J | 12 | | | ALL |
| 204Z | | | ID | | 0-0 | 34-61-24 | D04505J | 14 | | | D04965J | | | ID | ALL |
| 205 | 20 | UA | | | 1-6 | SPARE | D04965J | | | IE | GD00553 | S.. | 2 | | ALL |
| 205B | 24 | PW | IE | | 25-0 | SPARE | D04505J | 16 | | | D04965J | 16 | | | ALL |
| 205R | 24 | PW | IE | | 0-0 | SPARE | D04505J | 15 | | | D04965J | 15 | | | ALL |
| 205Z | | | IE | | 0-0 | SPARE | D04505J | 17 | | | D04965J | | | IE | ALL |
| 206 | 20 | UA | | | 1-6 | SPARE | D04965J | REF | | IF | GD00553 | S.. | 2 | | ALL |
| 206B | 24 | PW | IF | | 25-0 | SPARE | D04505J | REF | JB | | D04965J | REF | JW | | ALL |
| 206R | 24 | PW | IF | | 0-0 | SPARE | D04505J | REF | JB | | D04965J | REF | JW | | ALL |
| 206Z | | | IF | | 0-0 | SPARE | D04505J | REF | JB | | D04965J | REF | | IF | ALL |
| 209 | 20 | UA | | | 1-6 | SPARE | D04965J | | | II | GD00553 | S.. | 2 | | 150-154, 275-299 |
| 209B | 24 | PW | II | | 25-0 | SPARE | D04965J | 36 | | | D04505J | 36 | | | 150-154, 275-299 |
| 209R | 24 | PW | II | | 0-0 | SPARE | D04965J | 35 | | | D04505J | 35 | | | 150-154, 275-299 |
| 209Z | | | II | | 0-0 | SPARE | D04965J | | | II | D04505J | 37 | | | 150-154, 275-299 |
| 210 | 20 | UA | | | 1-6 | SPARE | D04965J | | | IJ | GD00553 | S.. | 2 | | 050-099 |
| 210 | 20 | UA | | | 1-6 | SPARE | GD00553 | S.. | 2 | | D04965J | | | IJ | 150-199, 275-299 |
| 210B | 24 | PW | IJ | | 53-0 | SPARE | D04965J | 49 | | | D04967J | 9 | | | 050-099 |
| 210B | 24 | PW | IJ | | 54-0 | SPARE | D04967J | 9 | | | D04965J | 49 | | | 150-199, 275-299 |
| 210R | 24 | PW | IJ | | 0-0 | SPARE | D04965J | 48 | | | D04967J | 8 | | | 050-099 |
| 210R | 24 | PW | IJ | | 0-0 | SPARE | D04967J | 8 | | | D04965J | 48 | | | 150-199, 275-299 |
| 210Z | | | IJ | | 0-0 | SPARE | D04965J | | | IJ | D04967J | 10 | | | 050-099 |
| 210Z | | | IJ | | 0-0 | SPARE | D04967J | 10 | | | D04965J | | | IJ | 150-199, 275-299 |
| 212 | 20 | UA | | | 1-6 | 34-22-91 | D04965J | | | IL | GD00553 | S.. | 2 | | 050-099 |
| 212 | 20 | UA | | | 3-0 | 34-22-91 | D04965J | | | IL | GD00553 | S.. | 2 | | 150-199, 275-299 |
| 212B | 24 | PW | IL | | 53-0 | 34-22-91 | D04965J | 54 | | | D04967J | 14 | | | 050-099 |
| 212B | 24 | PW | IL | | 54-0 | 34-22-91 | D04965J | 54 | | | D04967J | 14 | | | 150-199, 275-299 |
| 212R | 24 | PW | IL | | 0-0 | 34-22-91 | D04965J | 53 | | | D04967J | 13 | | | ALL |
| 212Z | | | IL | | 0-0 | 34-22-91 | D04965J | | | IL | D04967J | 15 | | | ALL |
| 213 | 20 | UA | | | 1-6 | 22-14-21 | D04965J | | | IM | GD00553 | S.. | 2 | | ALL |
| 213B | 24 | PW | IM | | 25-0 | 22-14-21 | D04965J | 34 | | | D04505J | 34 | | | ALL |
| 213R | 24 | PW | IM | | 0-0 | 22-14-21 | D04965J | 33 | | | D04505J | 33 | | | ALL |
| 213Z | | | IM | | 0-0 | 22-14-21 | D04965J | | | IM | D04505J | 38 | | | ALL |
| 301B | 24 | PM | MA | | 25-0 | 34-12-21 | D04505J | 7 | | | D04965J | 7 | | | ALL |
| 301R | 24 | PM | MA | | 0-0 | 34-12-21 | D04505J | 6 | | | D04965J | 6 | | | ALL |
| 301Y | 24 | PM | MA | | 0-0 | 34-12-21 | D04505J | 8 | | | D04965J | 8 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0850

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|---------|-------|------|------|------------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | |
| W0855 | 286T0855 | | | ADC-R AND FMC-R,SHELF TO F/O INSTR PNL (continued) | | | | | | | | | | |
| FRA | | | | | 0-0 | 34-13-21 | D04965J | | IB | D04965J | 11 | | | ALL |
| FRB | | | | | 0-0 | SPARE | D04965J | | IE | D04965J | 17 | | | ALL |
| FRC | | | | | 0-0 | SPARE | D04965J | REF | IF | D04965J | CAP | Y | | ALL |
| FRD | | | | | 0-0 | 34-61-24 | D04965J | | ID | D04965J | 14 | | | ALL |
| FRE | | | | | 0-0 | SPARE | D04965J | | IC | D04965J | 23 | | | 150-154, 275-299 |
| FRF | | | | | 0-0 | SPARE | D04965J | | II | D04965J | 37 | | | 150-154, 275-299 |
| FRG | | | | | 0-0 | 34-22-93 | D04965J | | IL | D04965J | 55 | | | 050-099 |
| FRJ | | | | | 0-0 | SPARE | D04965J | | IJ | D04965J | 50 | | | ALL |
| FRL | | | | | 0-0 | 34-22-91 | D04965J | | IL | D04965J | 55 | | | 150-199, 275-299 |
| FRM | | | | | 0-0 | 22-14-21 | D04965J | | IM | D04965J | 38 | | | ALL |
| W0857 | 286T0857 | | | COAX CABLE-E2-5 TO FWD ZONE MULTIPLEXER | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-34-14 | D00531 | = C1 | | D05303J | = C1 | | | ALL |
| 01CX | | | | BX A | 18-0 | 23-34-14 | D00531 | = A1 | | D05303J | = A1 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0850
Page 5 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|--------------------------------------|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0863 | 286T0863 | | | E2-5 TO M51 PILOTS CALL PANEL | | | | | | | | | | | |
| 001 | 22 | PA | | | 35-0 | 23-42-11 | D00735 | | 20 | | D05001J | | 1 | | ALL |
| 002 | 22 | PA | | | 35-0 | 23-42-11 | D00735 | | 23 | | D05001J | | 2 | | ALL |
| 003 | 22 | PA | | | 35-0 | 23-42-11 | D00735 | | 26 | | D05001J | | 3 | | ALL |
| 004 | 22 | PA | | | 35-0 | 23-42-11 | D00735 | | 29 | | D05001J | | 4 | | ALL |
| 005 | 22 | PQ | AE | | 35-0 | 23-42-11 | D00735 | | 21 | | D05001J | | 5 | | ALL |
| 005Z | | | AE | | 0-0 | 23-42-11 | D00735 | | 24 | | D05001J | | 6 | | ALL |
| 006 | 24 | PV | AF | | 7-0 | 21-58-11 | D00735 | | 45 | | TB0066Z | | 23 | BJ | ALL |
| 006Z | | | AF | | 0-0 | 21-58-11 | D00735 | DED | | | TB0066Z | | DED | | ALL |
| 007 | 24 | PK | | | 7-0 | 21-58-11 | D00735 | | 42 | | TB0066Y | C015 | BJ | | ALL |
| 008 | 24 | PK | | | 36-0 | 23-32-12 | D01655 | | 5 | | D05001J | | 11 | | ALL |
| 009 | 22 | PQ | AI | | 8-0 | 33-16-17 | D01655 | | 3 | | TB0066Y | C031 | BJ | | ALL |
| 009Z | | | AI | | 0-0 | 33-16-17 | D01655 | DED | | | TB0066Y | | DED | | ALL |
| 010 | 22 | PQ | AJ | | 8-0 | 33-16-17 | D01655 | | 4 | | TB0066Z | | 34 | BJ | ALL |
| 010Z | | | AJ | | 0-0 | 33-16-17 | D01655 | DED | | | TB0066Z | | DED | | ALL |
| 012 | 22 | PA | | | 35-0 | 23-42-11 | D00735 | | 36 | | D05001J | | 12 | | 280-299 |
| 013 | 20 | PA | | | 6-0 | 23-43-11 | D00735 | | 37 | | GD00265 | D.. | 2 | | 050-099 |
| 013 | 20 | PA | | | 7-0 | 23-43-11 | D00735 | | 37 | | GD00265 | D.. | 2 | | 150-199, 275-299 |
| 014 | 22 | PA | | | 8-0 | 31-51-33 | D00735 | | 32 | | TB0070X | D010 | BJ | | ALL |
| 015 | 22 | PA | | | 35-0 | 23-43-11 | D00735 | | 39 | | D05001J | | 13 | | ALL |
| 016 | 22 | PA | | | 35-0 | 23-43-11 | D00735 | | 44 | | D05001J | | 14 | | ALL |
| 017 | 22 | PA | | | 35-0 | 23-43-11 | D00735 | | 38 | | D05001J | | 15 | | ALL |
| 018 | 22 | PA | | | 7-0 | 23-43-11 | D00735 | | 33 | | TB0066X | A007 | BJ | | ALL |
| 019 | 24 | PK | | | 35-0 | 23-21-11 | D00735 | | 3 | | D05001J | | 16 | | ALL |
| 020 | 24 | PK | | | 35-0 | 23-21-11 | D00735 | | 4 | | D05001J | | 17 | | ALL |
| 022 | 24 | PK | | | 35-0 | 23-21-11 | D00735 | | 6 | | D05001J | | 19 | | ALL |
| 023 | 24 | PK | | | 35-0 | 23-21-11 | D00735 | | 7 | | D05001J | | 20 | | ALL |
| 024 | 24 | PK | | | 35-0 | 23-21-11 | D00735 | | 13 | | D05001J | | 21 | | ALL |
| 025 | 24 | PK | | | 35-0 | 23-21-11 | D00735 | | 14 | | D05001J | | 22 | | ALL |
| 027 | 24 | PK | | | 35-0 | 23-21-11 | D00735 | | 16 | | D05001J | | 24 | | ALL |
| 028 | 24 | PK | | | 35-0 | 23-21-11 | D00735 | | 17 | | D05001J | | 25 | | ALL |
| 029 | 24 | PK | | | 35-0 | 23-21-11 | D00735 | | 8 | | D05001J | | 26 | | ALL |
| 030 | 24 | PK | | | 35-0 | 23-21-11 | D00735 | | 9 | | D05001J | | 27 | | ALL |
| 032 | 24 | PK | | | 35-0 | 23-21-11 | D00735 | | 11 | | D05001J | | 29 | | ALL |
| 033 | 24 | PK | | | 35-0 | 23-21-11 | D00735 | | 12 | | D05001J | | 30 | | ALL |
| 034 | 20 | PA | | | 8-0 | 33-13-16 | D00735 | | 1 | | TB0068H | | 3 | 2 | ALL |
| 035 | 20 | PA | | | 6-0 | 33-13-16 | D00735 | | 2 | | GD00263 | A.. | 2 | | 050-099 |
| 035 | 20 | PA | | | 7-0 | 33-13-16 | D00735 | | 2 | | GD00263 | A.. | 2 | | 150-199, 275-299 |
| 036 | 22 | PQ | BK | | 8-0 | 33-16-17 | D00735 | | 40 | | TB0068Z | | 21 | BJ | ALL |
| 036Z | | | BK | | 0-0 | 33-16-17 | D00735 | DED | | | TB0068Z | | DED | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0860

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0863 | 286T0863 | | | E2-5 TO M51 PILOTS CALL PANEL (continued) | | | | | | | | | | | |
| 037 | 22 | PQ | BL | 8-0 | 33-16-17 | D00735 | | 41 | | TB0068Y | A020 | BJ | | ALL | |
| 037Z | | | BL | 0-0 | 33-16-17 | D00735 | | DED | | TB0068Y | DED | | | ALL | |
| 038 | 24 | PK | | 35-0 | 23-22-11 | D00735 | | 50 | | D05001J | 8 | | | ALL | |
| 043 | 20 | PA | | 8-0 | 33-13-16 | D01655 | | 1 | | TB0064G | 3 | 2 | | 050-099, 150-199 | |
| 044 | 20 | PA | | 6-0 | 33-13-16 | D01655 | | 2 | | GD00267 | A.. | 2 | | 050-099 | |
| 044 | 20 | PA | | 7-0 | 33-13-16 | D01655 | | 2 | | GD00267 | A.. | 2 | | 150-199 | |
| 046 | 22 | PA | | 35-0 | 23-42-11 | D00735 | | 46 | | D05001J | 7 | | | ALL | |
| 048 | 24 | PK | | 35-0 | 23-21-11 | D00735 | | 48 | | D05001J | 28 | | | ALL | |
| 049 | 24 | PK | | 35-0 | 23-21-11 | D00735 | | 49 | | D05001J | 23 | | | ALL | |
| 051 | 24 | PK | | 35-0 | 23-21-11 | D00735 | | 51 | | D05001J | 18 | | | ALL | |
| 066 | 22 | PA | | 36-0 | 23-24-11 | D05001J | | 31 | | D01655 | 7 | | | 050-099 | |
| 066 | 22 | PA | | 36-0 | 23-24-11 | D01655 | | 7 | | D05001J | 31 | | | 150-199 | |
| 067 | 22 | PA | | 36-0 | 23-24-11 | D05001J | | 32 | | D01655 | 6 | | | 050-099 | |
| 067 | 22 | PA | | 36-0 | 23-24-11 | D01655 | | 6 | | D05001J | 32 | | | 150-199 | |
| 068 | 22 | PA | | 35-0 | 23-42-11 | D00735 | | 47 | | D05001J | 9 | | | 050-099, 162-199 | |
| 069 | 22 | PA | | 35-0 | 23-42-11 | D00735 | | 52 | | D05001J | 38 | | | 050-099, 162-199 | |
| 070 | 22 | PA | | 35-0 | 23-42-11 | D00735 | | 53 | | D05001J | 39 | | | 050-099, 162-199 | |
| 071 | 22 | PA | | 35-0 | 23-42-11 | D00735 | | 54 | | D05001J | 40 | | | 050-099, 162-199 | |
| W0864 | 286T0864 | | | RIGHT MAIN GEAR UPPER J-BOX-SYS 2 | | | | | | | | | | | |
| 201B | 18 | UB | A | 17-0 | 32-61-12 | D05190P | | 2 | | D05030P | 2 | | | 050-099 | |
| 201B | 18 | UB | A | 19-0 | 32-61-12 | D05190P | | 2 | | D05030P | 2 | | | 150-199, 275-299 | |
| 201R | 18 | UB | A | 0-0 | 32-61-12 | D05190P | | 1 | | D05030P | 1 | | | ALL | |
| 202B | 18 | UB | B | 17-0 | 32-61-12 | D05190P | | 4 | | D05030P | 4 | | | 050-099 | |
| 202B | 18 | UB | B | 19-0 | 32-61-12 | D05190P | | 4 | | D05030P | 4 | | | 150-199, 275-299 | |
| 202R | 18 | UB | B | 0-0 | 32-61-12 | D05190P | | 3 | | D05030P | 3 | | | ALL | |
| 203B | 18 | UB | C | 17-0 | 32-09-12 | D05190P | | 11 | | D05030P | 6 | | | 050-099 | |
| 203B | 18 | UB | C | 19-0 | 32-09-12 | D05190P | | 11 | | D05030P | 6 | | | 150-199, 275-299 | |
| 203R | 18 | UB | C | 0-0 | 32-09-12 | D05190P | | 10 | | D05030P | 5 | | | ALL | |
| 204B | 20 | VG | D | 17-0 | 32-42-11 | D05190P | | 17 | | D05030P | 8 | | | 050-099 | |
| 204B | 20 | VG | D | 19-0 | 32-42-11 | D05190P | | 17 | | D05030P | 8 | | | 150-199, 275-299 | |
| 204R | 20 | VG | D | 0-0 | 32-42-11 | D05190P | | 16 | | D05030P | 7 | | | ALL | |
| 204Z | | | D | 0-0 | 32-42-11 | D05190P | | 14 | | D05030P | 17 | | | ALL | |
| 205B | 20 | VG | E | 17-0 | 32-42-11 | D05190P | | 19 | | D05030P | 10 | | | 050-099 | |
| 205B | 20 | VG | E | 19-0 | 32-42-11 | D05190P | | 19 | | D05030P | 10 | | | 150-199, 275-299 | |
| 205R | 20 | VG | E | 0-0 | 32-42-11 | D05190P | | 18 | | D05030P | 9 | | | ALL | |
| 205Z | | | E | 0-0 | 32-42-11 | D05190P | | 15 | | D05030P | 18 | | | ALL | |
| 207B | 20 | VG | K | 20-0 | 32-45-14 | D06342P | | 9 | | D05030P | 15 | | | 050-099 | |
| 207B | 20 | VG | K | 18-0 | 32-45-14 | D06342P | | 9 | | D05030P | CAP | Y | | 150-154 | |

WIRE LIST

D280T132

91-21-11

Section W0860

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------|--|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0864 | 286T0864 | | | | RIGHT MAIN GEAR UPPER J-BOX-SYS 2 (continued) | | | | | | | | | | |
| 207B | 20 | VG | K | 19-0 | 32-45-14 | D06342P | | 9 | | | D05030P | 15 | | | 155-199, 275-299 |
| 207R | 20 | VG | K | 0-0 | 32-45-14 | D06342P | | 10 | | | D05030P | 16 | | | 050-099, 155-199, 275-299 |
| 207R | 20 | VG | K | 0-0 | 32-45-14 | D06342P | | 10 | | | D05030P | CAP | Y | | 150-154 |
| 207Z | | | | 0-0 | 32-45-14 | D06342P | | 11 | | | D05030P | 19 | | | |
| 207Z | | | K | 0-0 | 32-45-14 | D06342P | | 11 | | | D05030P | DED | | | 150-154 |
| 208B | 20 | VG | L | 20-0 | 32-45-14 | D06342P | | 12 | | | D05030P | 28 | | | 050-099 |
| 208B | 20 | VG | L | 18-0 | 32-45-14 | D06342P | | 12 | | | D05030P | CAP | Y | | 150-154 |
| 208B | 20 | VG | L | 19-0 | 32-45-14 | D06342P | | 12 | | | D05030P | 28 | | | 155-199, 275-299 |
| 208R | 20 | VG | L | 0-0 | 32-45-14 | D06342P | | 13 | | | D05030P | 29 | | | 050-099, 155-199, 275-299 |
| 208R | 20 | VG | L | 0-0 | 32-45-14 | D06342P | | 13 | | | D05030P | CAP | Y | | 150-154 |
| 208Z | | | | 0-0 | 32-45-14 | D06342P | | 14 | | | D05030P | 30 | | | |
| 208Z | | | L | 0-0 | 32-45-14 | D06342P | | 14 | | | D05030P | DED | | | 150-154 |
| 301B | 20 | VH | CO | 19-0 | 27-62-11 | D05190P | | 12 | | | D05030P | 20 | | | ALL |
| 301R | 20 | VH | CO | 0-0 | 27-62-11 | D05190P | | 13 | | | D05030P | 21 | | | ALL |
| 301Y | 20 | VH | CO | 0-0 | 27-62-11 | D05190P | | 9 | | | D05030P | 22 | | | ALL |
| 301Z | | | CO | 0-0 | 27-62-11 | D05190P | | =CC | M | | D05030P | =CC | M | | ALL |
| 451G | 18 | UY | F | 17-0 | 32-46-11 | D05190P | | 6 | 4G | | D05030P | 12 | 4H | | ALL |
| 451W | 18 | UY | F | 0-0 | 32-46-11 | D05190P | | 5 | 4K | | D05030P | 11 | 4L | | ALL |
| 452G | 18 | UY | G | 17-0 | 32-46-11 | D05190P | | 8 | 4G | | D05030P | 14 | 4H | | ALL |
| 452W | 18 | UY | G | 0-0 | 32-46-11 | D05190P | | 7 | 4K | | D05030P | 13 | 4L | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0860

Page 3 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0873 | 286T0873 | | | RIGHT-FWD ZONE SEAT ELECTRONICS BOX TO NO.1 COLUMN TIMER DECODER | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-34-15 | D00525 | =C1 | | | | D00605 | =CF | | ALL |
| 01CX | | | | BX | 43-0 | 23-34-15 | D00525 | =A1 | | | | D00605 | F | | 050-099 |
| 01CX | | | | BX | 21-0 | 23-34-15 | D00525 | =A1 | | | | D00605 | F | | 150-157, 276-299 |
| 01CX | | | | BX | 25-0 | 23-34-15 | D00525 | =A1 | | | | D00605 | F | | 162-199 |
| 01CX | | | | BX | 19-0 | 23-34-15 | D00525 | =A1 | | | | D00605 | F | | 275 |
| 02CO | | | | B | 0-0 | 23-34-15 | D02575 | =C1 | | | | D06107J | C15 | | 050-099, 162-199 |
| 02CX | | | | BX | 33-0 | 23-34-15 | D02575 | =A1 | | | | D06107J | 15 | | 050-099 |
| 02CX | | | | BX | 34-0 | 23-34-15 | D02575 | =A1 | | | | D06107J | 15 | | 162-199 |
| 201B | 20 | | | PB | 29-0 | 23-34-15 | SM00006 | | | S | | D00605 | B | | 050-099 |
| 201B | 20 | | | PB | 19-0 | 23-34-15 | D00499 | | 5 | | | D00605 | B | | 150-157, 276-299 |
| 201B | 20 | | | PB | 12-0 | 23-34-15 | SM00006 | | | S | | D00605 | B | | 162-199 |
| 201B | 20 | | | PB | 17-0 | 23-34-15 | D00499 | | 5 | | | D00605 | B | | 275 |
| 201R | 20 | | | PB | 0-0 | 23-34-15 | SM00005 | | | S | | D00605 | A | | 050-099, 162-199 |
| 201R | 20 | | | PB | 0-0 | 23-34-15 | D00499 | | 4 | | | D00605 | A | | 150-157, 275-299 |
| 202B | 20 | | | PB | 21-0 | 23-34-15 | SM00006 | | | S | | D06107J | 2 | | 050-099 |
| 202B | 20 | | | PB | 22-0 | 23-34-15 | SM00006 | | | S | | D06107J | 2 | | 162-199 |
| 202R | 20 | | | PB | 0-0 | 23-34-15 | SM00005 | | | S | | D06107J | 1 | | 050-099, 162-199 |
| 203B | 20 | | | PB | 13-0 | 23-34-15 | SM00006 | | | S | | D00499 | 5 | | 050-099 |
| 203B | 20 | | | PB | 13-0 | 23-34-15 | D00499 | | 5 | | | SM00006 | | S | 162-199 |
| 203R | 20 | | | PB | 0-0 | 23-34-15 | SM00005 | | | S | | D00499 | 4 | | 050-099, 162-199 |
| 301B | 24 | | | PM | 30-0 | 23-34-15 | SM00002 | | | W | | D00605 | D | | 050-099 |
| 301B | 24 | | | PM | 19-0 | 23-34-15 | D00499 | | 2 | | | D00605 | D | | 150-157, 276-299 |
| 301B | 24 | | | PM | 12-0 | 23-34-15 | SM00002 | | | S | | D00605 | D | | 162-199 |
| 301B | 24 | | | PM | 17-0 | 23-34-15 | D00499 | | 2 | | | D00605 | D | | 275 |
| 301R | 24 | | | PM | 0-0 | 23-34-15 | SM00001 | | | S | | D00605 | E | | 050-099, 162-199 |
| 301R | 24 | | | PM | 0-0 | 23-34-15 | D00499 | | 1 | | | D00605 | E | | 150-157, 275-299 |
| 301Y | 24 | | | PM | 0-0 | 23-34-15 | SM00004 | | | S | | D00605 | C | | 050-099, 162-199 |
| 301Y | 24 | | | PM | 0-0 | 23-34-15 | D00499 | | 3 | | | D00605 | C | | 150-157, 275-299 |
| 302B | 24 | | | PM | 21-0 | 23-34-15 | SM00002 | | | W | | D06107J | 5 | | 050-099 |
| 302B | 24 | | | PM | 22-0 | 23-34-15 | SM00002 | | | S | | D06107J | 5 | | 162-199 |
| 302R | 24 | | | PM | 0-0 | 23-34-15 | SM00003 | | | S | | D06107J | 4 | | 050-099, 162-199 |
| 302Y | 24 | | | PM | 0-0 | 23-34-15 | SM00004 | | | S | | D06107J | 3 | | 050-099, 162-199 |
| 303B | 24 | | | PM | 13-0 | 23-34-15 | SM00003 | | | S | | D00499 | 2 | | 050-099 |
| 303B | 24 | | | PM | 13-0 | 23-34-15 | D00499 | | 2 | | | SM00003 | | S | 162-199 |
| 303R | 24 | | | PM | 0-0 | 23-34-15 | SM00001 | | | S | | D00499 | 1 | | 050-099 |
| 303R | 24 | | | PM | 0-0 | 23-34-15 | D00499 | | 1 | | | SM00001 | | S | 162-199 |
| 303Y | 24 | | | PM | 0-0 | 23-34-15 | SM00004 | | | S | | D00499 | 3 | | 050-099 |
| 303Y | 24 | | | PM | 0-0 | 23-34-15 | D00499 | | 3 | | | SM00004 | | S | 162-199 |

WIRE LIST

D280T132

91-21-11

Section W0870

Page 1

Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | |
|--------------|-----------------|--|-------|-------------|----------|--------|---------|-------|------|------|--------|-------|-------------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term |
| W0875 | 286T0875 | CENTER-FWD ZONE SEAT ELECTRONICS BOX TO NO.1 COLUMN TIMER DECODER | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-34-17 | D00527 | | =C1 | | | D00607 | | =CF | ALL |
| 01CX | | | BX A | 36-1 | 23-34-17 | D00527 | | =A1 | | | D00607 | | F | 050-099, 162-199 |
| 01CX | | | BX A | 22-0 | 23-34-17 | D00527 | | =A1 | | | D00607 | | F | 150-157, 275-299 |
| 201B | 20 | | PB IA | 34-7 | 23-34-17 | D00503 | | 5 | | | D00607 | | B | 050-099, 162-199 |
| 201B | 20 | | PB IA | 20-0 | 23-34-17 | D00503 | | 5 | | | D00607 | | B | 150-157, 275-299 |
| 201R | 20 | | PB IA | 0-0 | 23-34-17 | D00503 | | 4 | | | D00607 | | A | ALL |
| 301B | 24 | | PM MA | 34-7 | 23-34-17 | D00503 | | 2 | | | D00607 | | D | 050-099, 162-199 |
| 301B | 24 | | PM MA | 22-0 | 23-34-17 | D00503 | | 2 | | | D00607 | | D | 150-157, 275-299 |
| 301R | 24 | | PM MA | 0-0 | 23-34-17 | D00503 | | 1 | | | D00607 | | E | ALL |
| 301Y | 24 | | PM MA | 0-0 | 23-34-17 | D00503 | | 3 | | | D00607 | | C | ALL |
| W0877 | 286T0877 | LEFT-FWD ZONE SEAT ELECTRONICS BOX TO NO.1 COLUMN TIMER DECODER | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-34-16 | D00529 | | =C1 | | | D00609 | | =CF | ALL |
| 01CX | | | BX A | 51-0 | 23-34-16 | D00529 | | =A1 | | | D00609 | | F | 050-099 |
| 01CX | | | BX A | 32-0 | 23-34-16 | D00529 | | =A1 | | | D00609 | | F | 150-199 |
| 01CX | | | BX A | 26-0 | 23-34-16 | D00529 | | =A1 | | | D00609 | | F | 275 |
| 01CX | | | BX A | 27-0 | 23-34-16 | D00529 | | =A1 | | | D00609 | | F | 276-299 |
| 201B | 20 | | PB IA | 51-0 | 23-34-16 | D00507 | | 5 | | | D00609 | | B | 050-099 |
| 201B | 20 | | PB IA | 32-0 | 23-34-16 | D00507 | | 5 | | | D00609 | | B | 150-199 |
| 201B | 20 | | PB IA | 26-0 | 23-34-16 | D00507 | | 5 | | | D00609 | | B | 275 |
| 201B | 20 | | PB IA | 27-0 | 23-34-16 | D00507 | | 5 | | | D00609 | | B | 276-299 |
| 201R | 20 | | PB IA | 0-0 | 23-34-16 | D00507 | | 4 | | | D00609 | | A | ALL |
| 301B | 24 | | PM MA | 51-0 | 23-34-16 | D00507 | | 2 | | | D00609 | | D | 050-099 |
| 301B | 24 | | PM MA | 32-0 | 23-34-16 | D00507 | | 2 | | | D00609 | | D | 150-199 |
| 301B | 24 | | PM MA | 26-0 | 23-34-16 | D00507 | | 2 | | | D00609 | | D | 275 |
| 301B | 24 | | PM MA | 27-0 | 23-34-16 | D00507 | | 2 | | | D00609 | | D | 276-299 |
| 301R | 24 | | PM MA | 0-0 | 23-34-16 | D00507 | | 1 | | | D00609 | | E | ALL |
| 301Y | 24 | | PM MA | 0-0 | 23-34-16 | D00507 | | 3 | | | D00609 | | C | ALL |
| W0879 | 286T0879 | RIGHT-AFT ZONE SEAT ELECTRONICS BOX TO NO.2 COLUMN TIMER DECODER | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-34-15 | D00539 | | =C1 | | | D00617 | | =CF | ALL |
| 01CX | | | BX A | 86-4 | 23-34-15 | D00539 | | =A1 | | | D00617 | | F | 050-099 |
| 01CX | | | BX A | 76-6 | 23-34-15 | D00539 | | =A1 | | | D00617 | | F | 150-199 |
| 01CX | | | BX A | 25-10 | 23-34-15 | D00539 | | =A1 | | | D00617 | | F | 275-299 |
| 201B | 20 | | PB IA | 83-1 | 23-34-15 | D00513 | | 5 | | | D00617 | | B | 050-099 |
| 201B | 20 | | PB IA | 73-4 | 23-34-15 | D00513 | | 5 | | | D00617 | | B | 150-199 |
| 201B | 20 | | PB IA | 22-7 | 23-34-15 | D00513 | | 5 | | | D00617 | | B | 275-299 |
| 201R | 20 | | PB IA | 0-0 | 23-34-15 | D00513 | | 4 | | | D00617 | | A | ALL |
| 301B | 24 | | PM MA | 83-1 | 23-34-15 | D00513 | | 2 | | | D00617 | | D | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0870

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0879 | 286T0879 | | | RIGHT-AFT ZONE SEAT ELECTRONICS BOX TO NO.2 COLUMN TIMER DECODER (continued) | | | | | | | | | | | |
| 301B | 24 | PM | MA | | 73-4 | 23-34-15 | D00513 | | 2 | | D00617 | | D | | 150-199 |
| 301B | 24 | PM | MA | | 22-7 | 23-34-15 | D00513 | | 2 | | D00617 | | D | | 275-299 |
| 301R | 24 | PM | MA | | 0-0 | 23-34-15 | D00513 | | 1 | | D00617 | | E | | ALL |
| 301Y | 24 | PM | MA | | 0-0 | 23-34-15 | D00513 | | 3 | | D00617 | | C | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0870
Page 3 End
Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-------------|-----------------|-------|-------------|--|--------|---------|-------|------|------|--------|-------|-------------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W0881 | | 286T0881 | | | CENTER-AFT ZONE SEAT ELECTRONICS BOX TO NO.2 COLUMN TIMER DECODER | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-34-17 | D00541 | | = C1 | | | D00619 | | = CF | | ALL |
| 01CX | | | BX A | 83-0 | 23-34-17 | D00541 | | = A1 | | | D00619 | | F | | 050-099 |
| 01CX | | | BX A | 50-0 | 23-34-17 | D00541 | | = A1 | | | D00619 | | F | | 150-199, 275-299 |
| 201B | 20 | | PB IA | 85-0 | 23-34-17 | D00517 | | 5 | | | D00619 | | B | | 050-099 |
| 201B | 20 | | PB IA | 51-0 | 23-34-17 | D00517 | | 5 | | | D00619 | | B | | 150-199 |
| 201B | 16 | | PB IA | 51-0 | 23-34-17 | D00517 | | 5 | FL | | D00619 | | B | FM | 275-299 |
| 201R | 20 | | PB IA | 0-0 | 23-34-17 | D00517 | | 4 | | | D00619 | | A | | 050-099, 150-199 |
| 201R | 16 | | PB IA | 0-0 | 23-34-17 | D00517 | | 4 | FL | | D00619 | | A | FM | 275-299 |
| 301B | 24 | | PM MA | 85-0 | 23-34-17 | D00517 | | 2 | | | D00619 | | D | | 050-099 |
| 301B | 24 | | PM MA | 51-0 | 23-34-17 | D00517 | | 2 | | | D00619 | | D | | 150-199, 275-299 |
| 301R | 24 | | PM MA | 0-0 | 23-34-17 | D00517 | | 1 | | | D00619 | | E | | ALL |
| 301Y | 24 | | PM MA | 0-0 | 23-34-17 | D00517 | | 3 | | | D00619 | | C | | ALL |
| W0883 | | 286T0883 | | | LEFT-AFT ZONE SEAT ELECTRONICS BOX TO NO.2 COLUMN TIMER DECODER | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-34-16 | D00543 | | = C1 | | | D00621 | | = CF | | ALL |
| 01CX | | | BX A | 89-0 | 23-34-16 | D00543 | | = A1 | | | D00621 | | F | | 050-099 |
| 01CX | | | BX A | 83-0 | 23-34-16 | D00543 | | = A1 | | | D00621 | | F | | 150-199 |
| 01CX | | | BX A | 34-0 | 23-34-16 | D00543 | | = A1 | | | D00621 | | F | | 275-299 |
| 201B | 20 | | PB IA | 89-0 | 23-34-16 | D00521 | | 5 | | | D00621 | | B | | 050-099 |
| 201B | 20 | | PB IA | 85-0 | 23-34-16 | D00521 | | 5 | | | D00621 | | B | | 150-199 |
| 201B | 20 | | PB IA | 35-0 | 23-34-16 | D00521 | | 5 | | | D00621 | | B | | 275-299 |
| 201R | 20 | | PB IA | 0-0 | 23-34-16 | D00521 | | 4 | | | D00621 | | A | | ALL |
| 301B | 24 | | PM MA | 89-0 | 23-34-16 | D00521 | | 2 | | | D00621 | | D | | 050-099 |
| 301B | 24 | | PM MA | 85-0 | 23-34-16 | D00521 | | 2 | | | D00621 | | D | | 150-199 |
| 301B | 24 | | PM MA | 35-0 | 23-34-16 | D00521 | | 2 | | | D00621 | | D | | 275-299 |
| 301R | 24 | | PM MA | 0-0 | 23-34-16 | D00521 | | 1 | | | D00621 | | E | | ALL |
| 301Y | 24 | | PM MA | 0-0 | 23-34-16 | D00521 | | 3 | | | D00621 | | C | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0880

Page 1 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0892 | 286T0892 | | | P89-L2-INTEGRATION | | | | | | | | | | | |
| 001 | 12 | | HA | | 2-0 | 28-31-22 | K02091 | A1 | N | | C00375 | A1 | M | | 150-154, 275 |
| 002 | 12 | | HA | | 2-0 | 28-31-22 | K02091 | B1 | N | | C00375 | B1 | M | | 150-154, 275 |
| 003 | 12 | | HA | | 2-0 | 28-31-22 | K02091 | C1 | N | | C00375 | C1 | M | | 150-154, 275 |
| 004 | 20 | | PA | | 2-0 | 28-31-22 | K02091 | X2 | C | | GDX0001 | D.. | 2 | | 150-154, 275 |
| 005 | 20 | | PA | | 2-0 | 28-31-22 | K02091 | X1 | C | | TB0450G | | 2 | 2 | 150-154, 275 |
| 009 | 22 | | PA | | 2-0 | 28-31-22 | D17072J | | 2 | | TB0450G | | 2 | 2 | 150-154, 275 |
| 010 | 20 | | PA | | 2-0 | 28-31-22 | GDX0001 | D.. | 2 | | D12156 | X2 | | | 150-154, 275 |
| 011 | 22 | | PA | | 3-0 | 28-31-22 | TB0450G | | 2 | 2 | D12156 | X1 | | | 150-154, 275 |
| 012 | 22 | | PQ | AL | 3-0 | 28-31-22 | D17080J | | 1 | | D12156 | A1 | | | 150-154, 275 |
| 012Z | | | | AL | 0-0 | 28-31-22 | D17080J | DED | | | D12156 | DED | | | 150-154, 275 |
| 013 | 22 | | PQ | AM | 3-0 | 28-31-22 | TB0450G | | 3 | 2 | D12156 | A2 | | | 150-154, 275 |
| 013Z | | | | AM | 0-0 | 28-31-22 | TB0450G | DED | | | D12156 | DED | | | 150-154, 275 |
| 014 | 22 | | PQ | AN | 3-0 | 28-31-22 | D17072J | | 5 | | D12156 | B1 | | | 150-154, 275 |
| 014Z | | | | AN | 0-0 | 28-31-22 | D17072J | DED | | | D12156 | DED | | | 150-154, 275 |
| 015 | 22 | | PQ | AO | 3-0 | 28-31-22 | D17074J | | 1 | | D12156 | B2 | | | 150-154, 275 |
| 015Z | | | | AO | 0-0 | 28-31-22 | D17074J | DED | | | D12156 | DED | | | 150-154, 275 |
| 016 | 22 | | PA | | 3-0 | 28-31-22 | D17072J | | 4 | | D12156 | C1 | | | 150-154, 275 |
| 017 | 22 | | PA | | 3-0 | 28-31-22 | D17072J | | 1 | | D12156 | C2 | | | 150-154, 275 |
| 018 | 22 | | PA | | 3-0 | 28-31-22 | D17072J | | 3 | | D12156 | D1 | | | 150-154, 275 |
| 019 | 20 | | PA | | 2-0 | 28-31-22 | GDX0001 | D.. | 2 | | D12156 | D2 | | | 150-154, 275 |
| 020 | 22 | | PQ | AT | 2-0 | 28-31-22 | D17074J | | 2 | | TB0450G | 3 | 2 | | 150-154, 275 |
| 020Z | | | | AT | 0-0 | 28-31-22 | D17074J | DED | | | TB0450G | DED | | | 150-154, 275 |
| 022 | 20 | | PQ | AV | 2-0 | 28-31-22 | D12160 | A3 | | | GDX0001 | D.. | 2 | | 150-154, 275 |
| 022Z | | | | AV | 0-0 | 28-31-22 | D12160 | DED | | | GDX0001 | DED | | | 150-154, 275 |
| 023 | 20 | | PA | | 2-0 | 28-31-22 | D12160 | X2 | | | GDX0001 | D.. | 2 | | 150-154, 275 |
| 024 | 22 | | PA | | 2-0 | 28-31-22 | D12160 | X1 | | | D17072J | 6 | | | 150-154, 275 |
| 025 | 22 | | PQ | AY | 2-0 | 28-31-22 | D12160 | A2 | | | D17072J | 9 | | | 150-154, 275 |
| 025Z | | | | AY | 0-0 | 28-31-22 | D12160 | DED | | | D17072J | DED | | | 150-154, 275 |
| 026 | 22 | | PA | | 2-0 | 28-31-22 | D12160 | C1 | | | D17080J | 6 | | | 150-154, 275 |
| 027 | 20 | | PA | | 2-0 | 28-31-22 | D17074J | | 4 | | D17080J | 5 | | | 150-154, 275 |
| 028 | 20 | | PA | | 2-0 | 28-31-22 | D17074J | | 3 | | D17080J | 4 | | | 150-154, 275 |
| 029 | 20 | | PA | | 2-0 | 28-31-22 | D17072J | | 8 | | D17080J | 3 | | | 150-154, 275 |
| 030 | 20 | | PA | | 2-0 | 28-31-22 | D17072J | | 7 | | D17080J | 2 | | | 150-154, 275 |
| 031 | 22 | | PQ | BF | 2-0 | 28-31-22 | D17074J | | 5 | | TB0450D | C001 | 2 | | 150-154, 275 |
| 031Z | | | | BF | 0-0 | 28-31-22 | D17074J | DED | | | TB0450D | DED | | | 150-154, 275 |
| 032 | 20 | | PA | | 2-0 | 28-31-22 | D12164 | | 7 | | GDX0001 | D.. | 2 | | 150-154, 275 |
| 033 | 22 | | PA | | 2-0 | 28-31-22 | D12164 | | 3 | | D17080J | 7 | | | 150-154, 275 |
| 034 | 20 | | PQ | BI | 2-0 | 28-31-22 | D12164 | | 2 | | GDX0001 | D.. | 2 | | 150-154, 275 |
| 034Z | | | | BI | 0-0 | 28-31-22 | D12164 | DED | | | GDX0001 | DED | | | 150-154, 275 |

WIRE LIST

D280T132

91-21-11

Section W0890

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|---------------------------------------|-----------------|----|-------|-----|-------------|---------|-------|------|------|---------|-------|------|------|--------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0892 | 286T0892 | | | | | | | | | | | | | | | |
| P89-L2-INTEGRATION (continued) | | | | | | | | | | | | | | | | |
| 035 | 22 | PQ | BJ | 3-0 | 28-31-22 | D12164 | | 4 | | TB0450D | C001 | 2 | | 150-154, 275 | | |
| 035Z | | | BJ | 0-0 | 28-31-22 | D12164 | | DED | | TB0450D | DED | | | 150-154, 275 | | |
| 036 | 22 | PQ | BK | 2-0 | 28-31-22 | TB0450D | | A001 | 2 | D17072J | 10 | | | 150-154, 275 | | |
| 036Z | | | BK | 0-0 | 28-31-22 | TB0450D | | DED | | D17072J | DED | | | 150-154, 275 | | |
| 037 | 22 | PQ | BL | 2-0 | 28-31-22 | TB0450D | | A001 | 2 | TB0452D | A001 | 2 | | 150-154, 275 | | |
| 037Z | | | BL | 0-0 | 28-31-22 | TB0450D | | DED | | TB0452D | DED | | | 150-154, 275 | | |
| 038 | 22 | PA | | 2-0 | 28-31-22 | D12244 | | 12 | | K02091 | 12 | C | | 150-154, 275 | | |
| 039 | 22 | PA | | 2-0 | 28-31-22 | D12244 | | 6 | | D17072J | 14 | | | 150-154, 275 | | |
| 040 | 20 | PA | | 2-0 | 28-31-22 | D12244 | | 2 | | GDX0001 | D.. | 2 | | 150-154, 275 | | |
| 041 | 22 | PA | | 2-0 | 28-31-22 | D12244 | | 1 | | D17072J | 13 | | | 150-154, 275 | | |
| 042 | 22 | PA | | 2-0 | 28-31-22 | D12244 | | 11 | | D17072J | 12 | | | 150-154, 275 | | |
| 043 | 22 | PA | | 2-0 | 28-31-22 | D12244 | | 9 | | D17072J | 11 | | | 150-154, 275 | | |
| 044 | 20 | PA | | 2-0 | 28-31-22 | K02091 | | 13 | C | GDX0001 | D.. | 2 | | 150-154, 275 | | |
| W0894 | 286T0894 | | | | | | | | | | | | | | | |
| P89-R2-INTEGRATION | | | | | | | | | | | | | | | | |
| 001 | 12 | HA | | 2-0 | 28-31-22 | K02092 | | A1 | N | C00376 | A1 | M | | 150-154, 275 | | |
| 002 | 12 | HA | | 2-0 | 28-31-22 | K02092 | | B1 | N | C00376 | B1 | M | | 150-154, 275 | | |
| 003 | 12 | HA | | 2-0 | 28-31-22 | K02092 | | C1 | N | C00376 | C1 | M | | 150-154, 275 | | |
| 004 | 20 | PA | | 2-0 | 28-31-22 | K02092 | | X2 | C | GDX0002 | D.. | 2 | | 150-154, 275 | | |
| 005 | 20 | PA | | 2-0 | 28-31-22 | K02092 | | X1 | C | TB0452G | 4 | 2 | | 150-154, 275 | | |
| 009 | 22 | PA | | 2-0 | 28-31-22 | D17076J | | 2 | | TB0452G | 4 | 2 | | 150-154, 275 | | |
| 010 | 20 | PA | | 3-0 | 28-31-22 | GDX0002 | | D.. | 2 | D12158 | X2 | | | 150-154, 275 | | |
| 011 | 22 | PA | | 2-0 | 28-31-22 | TB0452G | | 4 | 2 | D12158 | X1 | | | 150-154, 275 | | |
| 012 | 22 | PQ | AL | 2-0 | 28-31-22 | D17078J | | 1 | | D12158 | A1 | | | 150-154, 275 | | |
| 012Z | | | AL | 0-0 | 28-31-22 | D17078J | | DED | | D12158 | DED | | | 150-154, 275 | | |
| 013 | 22 | PQ | AM | 2-0 | 28-31-22 | D17076J | | 7 | | D12158 | A2 | | | 150-154, 275 | | |
| 013Z | | | AM | 0-0 | 28-31-22 | D17076J | | DED | | D12158 | DED | | | 150-154, 275 | | |
| 014 | 22 | PQ | AN | 2-0 | 28-31-22 | D17076J | | 6 | | D12158 | B1 | | | 150-154, 275 | | |
| 014Z | | | AN | 0-0 | 28-31-22 | D17076J | | DED | | D12158 | DED | | | 150-154, 275 | | |
| 015 | 22 | PQ | AO | 2-0 | 28-31-22 | D17076J | | 3 | | D12158 | B2 | | | 150-154, 275 | | |
| 015Z | | | AO | 0-0 | 28-31-22 | D17076J | | DED | | D12158 | DED | | | 150-154, 275 | | |
| 016 | 22 | PA | | 2-0 | 28-31-22 | D17076J | | 5 | | D12158 | C1 | | | 150-154, 275 | | |
| 017 | 22 | PA | | 2-0 | 28-31-22 | D17076J | | 1 | | D12158 | C2 | | | 150-154, 275 | | |
| 018 | 22 | PA | | 2-0 | 28-31-22 | D17076J | | 4 | | D12158 | D1 | | | 150-154, 275 | | |
| 019 | 20 | PA | | 3-0 | 28-31-22 | GDX0002 | | D.. | 2 | D12158 | D2 | | | 150-154, 275 | | |
| 021 | 22 | PQ | AU | 2-0 | 28-31-22 | D17076J | | 8 | | TB0450G | 3 | 2 | | 150-154, 275 | | |
| 021Z | | | AU | 0-0 | 28-31-22 | D17076J | | DED | | TB0450G | DED | | | 150-154, 275 | | |
| 022 | 20 | PQ | AV | 2-0 | 28-31-22 | GDX0002 | | D.. | 2 | D12162 | A3 | | | 150-154, 275 | | |
| 022Z | | | AV | 0-0 | 28-31-22 | GDX0002 | | DED | | D12162 | DED | | | 150-154, 275 | | |

WIRE LIST

D280T132

91-21-11

Section W0890

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|--|-------|-------------|------|----------|---------|-------|------|------|---------|-------|------|------|--------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0894 | 286T0894 | P89-R2-INTEGRATION (continued) | | | | | | | | | | | | | |
| 023 | 20 | PA | | | 2-0 | 28-31-22 | GDX0002 | D.. | 2 | | D12162 | X2 | | | 150-154, 275 |
| 024 | 22 | PA | | | 2-0 | 28-31-22 | D17076J | | 9 | | D12162 | X1 | | | 150-154, 275 |
| 025 | 22 | PQ | AY | | 2-0 | 28-31-22 | D17076J | | 15 | | D12162 | A2 | | | 150-154, 275 |
| 025Z | | | AY | | 0-0 | 28-31-22 | D17076J | DED | | | D12162 | DED | | | 150-154, 275 |
| 026 | 22 | PA | | | 2-0 | 28-31-22 | D17078J | | 3 | | D12162 | C1 | | | 150-154, 275 |
| 027 | 20 | PA | | | 2-0 | 28-31-22 | D17078J | | 7 | | D17076J | 13 | | | 150-154, 275 |
| 028 | 20 | PA | | | 2-0 | 28-31-22 | D17078J | | 6 | | D17076J | 12 | | | 150-154, 275 |
| 029 | 20 | PA | | | 2-0 | 28-31-22 | D17078J | | 5 | | D17076J | 11 | | | 150-154, 275 |
| 030 | 20 | PA | | | 2-0 | 28-31-22 | D17078J | | 4 | | D17076J | 10 | | | 150-154, 275 |
| 031 | 22 | PQ | BF | | 2-0 | 28-31-22 | TB0452D | C001 | 2 | | D17076J | 14 | | | 150-154, 275 |
| 031Z | | | BF | | 0-0 | 28-31-22 | TB0452D | DED | | | D17076J | DED | | | 150-154, 275 |
| 032 | 20 | PA | | | 2-0 | 28-31-22 | GDX0002 | D.. | 2 | | D12166 | 7 | | | 150-154, 275 |
| 033 | 22 | PA | | | 2-0 | 28-31-22 | D17078J | | 2 | | D12166 | 3 | | | 150-154, 275 |
| 034 | 20 | PQ | BI | | 2-0 | 28-31-22 | GDX0002 | D.. | 2 | | D12166 | 2 | | | 150-154, 275 |
| 034Z | | | BI | | 0-0 | 28-31-22 | GDX0002 | DED | | | D12166 | DED | | | 150-154, 275 |
| 035 | 22 | PQ | BJ | | 2-0 | 28-31-22 | TB0452D | C001 | 2 | | D12166 | 4 | | | 150-154, 275 |
| 035Z | | | BJ | | 0-0 | 28-31-22 | TB0452D | DED | | | D12166 | DED | | | 150-154, 275 |
| 036 | 22 | PQ | BK | | 2-0 | 28-31-22 | TB0452D | A001 | 2 | | D17076J | 16 | | | 150-154, 275 |
| 036Z | | | BK | | 0-0 | 28-31-22 | TB0452D | DED | | | D17076J | DED | | | 150-154, 275 |
| 038 | 22 | PA | | | 2-0 | 28-31-22 | D12240 | | 12 | | TB0452D | A002 | 2 | | 150-154, 275 |
| 039 | 22 | PA | | | 2-0 | 28-31-22 | D12240 | | 6 | | D17076J | 24 | | | 150-154, 275 |
| 040 | 20 | PA | | | 2-0 | 28-31-22 | D12240 | | 13 | | GDX0002 | D.. | 2 | | 150-154, 275 |
| 041 | 22 | PA | | | 2-0 | 28-31-22 | D12240 | | 1 | | D17076J | 23 | | | 150-154, 275 |
| 042 | 22 | PA | | | 2-0 | 28-31-22 | D12240 | | 11 | | D17076J | 18 | | | 150-154, 275 |
| 043 | 22 | PA | | | 2-0 | 28-31-22 | D12240 | | 9 | | D17076J | 17 | | | 150-154, 275 |
| 044 | 22 | PA | | | 2-0 | 28-31-22 | D12240 | | 5 | | D17076J | 22 | | | 150-154, 275 |
| 045 | 22 | PA | | | 2-0 | 28-31-22 | D12240 | | 3 | | D17076J | 21 | | | 150-154, 275 |
| 046 | 22 | PA | | | 2-0 | 28-31-22 | D12240 | | 7 | | D17076J | 20 | | | 150-154, 275 |
| 047 | 22 | PA | | | 2-0 | 28-31-22 | D12240 | | 14 | | D17076J | 19 | | | 150-154, 275 |
| 048 | 20 | PA | | | 2-0 | 28-31-22 | K02092 | | 13 | C | GDX0002 | D.. | 2 | | 150-154, 275 |
| 049 | 22 | PA | | | 2-0 | 28-31-22 | K02092 | | 12 | C | TB0452D | C002 | 2 | | 150-154, 275 |
| 050 | 22 | PA | | | 2-0 | 28-31-22 | TB0452D | C002 | 2 | | TB0452D | C003 | 2 | | 150-154, 275 |
| 051 | 22 | PA | | | 2-0 | 28-31-22 | D12242 | | 3 | | TB0452D | A003 | 2 | | 150-154, 275 |
| 052 | 22 | PA | | | 2-0 | 28-31-22 | D12242 | | 7 | | D17076J | 27 | | | 150-154, 275 |
| 053 | 22 | PA | | | 2-0 | 28-31-22 | D12242 | | 2 | | D17076J | 26 | | | 150-154, 275 |
| 054 | 22 | PA | | | 2-0 | 28-31-22 | D12242 | | 4 | | D17076J | 25 | | | 150-154, 275 |
| W0899 | 286T0899 | ELEC SPOILER CONT PCA 1,W/W DISC TO WING DISC | | | | | | | | | | | | | |
| 001 | 20 | UA | | | 1-0 | 27-61-13 | SM00001 | | | W | D05459J | | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0890
 Page 3
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0899 | 286T0899 | | | ELEC SPOILER CONT PCA 1,W/W DISC TO WING DISC (continued) | | | | | | | | | | | | | |
| 002 | 20 | | UA | | 1-0 | 27-61-13 | SM00002 | | | | W | | D05459J | 4 | | | ALL |
| 003 | 20 | | UA | | 1-0 | 27-61-13 | SM00001 | | | | W | | D05459J | 1 | | | ALL |
| 004 | 20 | | UA | | 1-0 | 27-61-13 | SM00002 | | | | W | | D05459J | 3 | | | ALL |
| 005 | 18 | | UA | | 2-0 | 27-61-13 | GD00451 | | S.. | N | | | D05459J | 10 | | | ALL |
| WBK | 20 | | 7N | 1B | 54-0 | 27-61-13 | D05233J | | | | 2 | | D05459J | 8 | | | ALL |
| WBKZ | | | | 1B | 0-0 | 27-61-13 | GD00427 | | S.. | N | | | GD00451 | S.. | N | | ALL |
| WBN | 20 | | 7N | 1B | 0-0 | 27-61-13 | D05233J | | | | 6 | | D05459J | 6 | | | ALL |
| WBU | 20 | | 7N | 1B | 0-0 | 27-61-13 | D05233J | | | | 3 | | SM00002 | | W | | ALL |
| WOR | 20 | | 7N | 1B | 0-0 | 27-61-13 | D05233J | | | | 5 | | D05459J | 5 | | | ALL |
| WRB | 20 | | 7N | 1B | 0-0 | 27-61-13 | D05233J | | | | 7 | | D05459J | 7 | | | ALL |
| WRD | 20 | | 7N | 1B | 0-0 | 27-61-13 | D05233J | | | | 1 | | SM00001 | | W | | ALL |
| WVI | 20 | | 7N | 1B | 0-0 | 27-61-13 | D05233J | | | | 4 | | D05459J | 9 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0890
Page 4 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0902 | 286T0902 | | | FWD & MAIN EQPT CTR LTG,FWD DR WRN & CONT | | | | | | | | | | | | | |
| 001 | 18 | PA | | 36-0 | 33-31-41 | D05648P | | 56 | | | | | S00357 | 2 | C | | ALL |
| 002 | 18 | PA | | 14-0 | 33-31-41 | S00357 | | 3 | C | | | | SP00238 | | S | | ALL |
| 003 | 16 | PA | | 2-0 | 33-31-41 | S00355 | | 6 | C | * | | | S00355 | 1 | C | | ALL |
| 004 | 16 | PA | | 29-0 | 33-31-41 | D05648P | | 40 | | | | | S00354 | 2 | C | | ALL |
| 005 | 16 | PA | | 27-0 | 33-31-41 | S00354 | | 1 | C | | | | S00355 | 3 | C | * | ALL |
| 006 | 16 | PA | | 2-0 | 33-31-41 | S00355 | | 4 | C | | | | S00355 | 3 | C | * | ALL |
| 007 | 16 | PA | | 31-0 | 33-31-41 | S00355 | | 2 | C | | | | S00356 | 1 | C | | ALL |
| 008 | 16 | PA | | 31-0 | 33-31-41 | S00355 | | 5 | C | | | | S00356 | 3 | C | | ALL |
| 009 | 16 | PA | | 7-0 | 33-31-41 | S00356 | | 2 | C | | | | SP00240 | | S | | ALL |
| 010 | 16 | PA | | 27-0 | 33-31-41 | S00354 | | 3 | C | | | | S00355 | 6 | C | * | ALL |
| 012 | 22 | PA | | 26-0 | 30-32-21 | D05656P | | 9 | | | | | D05648P | 9 | | | ALL |
| 018 | 18 | PA | | 15-0 | 33-31-11 | D05290P | | 11 | DL | | | | D05648P | 4 | DK | | ALL |
| 01A | 20 | PA | | 15-0 | 30-21-11 | D05648P | | 8 | | | | | D05290P | 5 | | | 050-099, 150-199 |
| 01B | 22 | PA | | 27-0 | 30-11-11 | D05906P | | 11 | | | | | D05648P | 32 | | | 050-099, 150-199 |
| 01C | 22 | PA | | 27-0 | 30-11-11 | D05906P | | 12 | | | | | D05648P | 33 | | | 050-099, 150-199 |
| 01D | 22 | PA | | 27-0 | 30-11-11 | D05906P | | 13 | | | | | D05648P | 34 | | | 050-099, 150-199 |
| 01E | 22 | PA | | 27-0 | 30-11-11 | D05906P | | 14 | | | | | D05648P | 35 | | | 050-099, 150-199 |
| 01F | 22 | PA | | 27-0 | 30-11-11 | D05906P | | 15 | | | | | D05648P | 36 | | | 050-099, 150-199 |
| 01H | 20 | PA | | 27-0 | 73-21-16 | D05906P | | 7 | | | | | D05648P | 21 | | | 050-099, 155-199 |
| 01J | 20 | PA | | 27-0 | 30-81-11 | D05906P | | 8 | | | | | D05648P | 22 | | | 050-099, 162-199 |
| 01J | 22 | PA | | 27-0 | 30-81-11 | D05906P | | 8 | | | | | D05648P | 22 | | | 150-157 |
| 01K | 20 | PA | | 27-0 | 30-81-11 | D05906P | | 9 | | | | | D05648P | 25 | | | 050-099, 150-199 |
| 01L | 20 | PA | | 14-0 | 30-81-11 | D12140 | | 1 | | | | | D05906P | 2 | | | 050-099, 150-199 |
| 01M | 20 | PA | | 26-0 | 30-81-11 | D12140 | | 2 | | | | | D05648P | 15 | | | 050-099, 150-199 |
| 01N | 20 | PA | | 3-0 | 30-81-11 | D12140 | | 3 | | | | | GD00595 | D.. | 2 | | 050-099, 150-199 |
| 01P | 20 | PA | | 26-0 | 30-81-11 | D12140 | | 4 | | | | | D05648P | 16 | | | 050-099, 150-199 |
| 01R | 20 | PA | | 14-0 | 30-81-11 | D12140 | | 5 | | | | | D05906P | 3 | | | 050-099, 150-199 |
| 01S | 20 | PA | | 26-0 | 30-81-11 | D12140 | | 6 | | | | | D05648P | 13 | | | 050-099, 150-199 |
| 01T | 20 | PA | | 3-0 | 30-81-11 | D12140 | | 7 | | | | | GD00595 | A.. | 2 | | 050-099, 150-199 |
| 01U | 20 | PA | | 3-0 | 30-81-11 | D12140 | | 8 | | | | | GD00595 | S.. | 2 | | 050-099, 150-199 |
| 01V | 20 | PA | | 26-0 | 30-81-11 | D12140 | | 12 | | | | | D05648P | 17 | | | 050-099, 150-199 |
| 01W | 24 | PK | | 27-0 | 21-51-11 | D05648P | | 1 | | | | | D05656P | 2 | | | 050-099 |
| 01W | 24 | PK | | 26-0 | 21-51-11 | D05648P | | 1 | | | | | D05656P | 2 | | | 150-199 |
| 022 | 24 | PK | | 15-0 | 30-34-41 | D05290P | | 4 | | | | | D05648P | 6 | | | 150-199 |
| 023 | 24 | PK | | 15-0 | 30-81-11 | D05290P | | 3 | | | | | D05648P | 20 | | | 050-099, 150-154, 156-157, 166-199 |
| 023 | 24 | PK | | 15-0 | 30-34-41 | D05290P | | 3 | | | | | D05648P | 5 | | | 155 |
| 023 | 24 | PK | | 15-0 | 30-81-11 | D05290P | | 3 | | | | | D05648P | 5 | | | 162-165 |
| 027 | 20 | PA | | 26-0 | 30-32-21 | D05656P | | 5 | | | | | D05648P | 12 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0900

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0902 | 286T0902 | | | FWD & MAIN EQPT CTR LTG,FWD DR WRN & CONT (continued) | | | | | | | | | | | | | |
| 030 | 20 | PA | | 26-0 | 33-11-14 | D05648P | | 10 | | | | | D05656P | 10 | | | ALL |
| 032 | 22 | PA | | 26-0 | 30-11-11 | D05656P | | 6 | | | | | D05648P | 14 | | | ALL |
| 033 | 22 | PA | | 26-0 | 30-11-11 | D05906P | | 18 | | | | | D05908P | 16 | | | 050-099, 150-154, 156-199 |
| 033 | 22 | PA | | 26-0 | 30-11-11 | D05908P | | 17 | | | | | D05906P | 18 | | | 155 |
| 033 | 22 | PA | | 26-0 | 30-11-11 | D05656P | | 7 | | | | | D05648P | 18 | | | 275-299 |
| 034 | 22 | PA | | 26-0 | 30-11-11 | D05906P | | 16 | | | | | D05908P | 17 | | | 050-099, 150-154, 156-199 |
| 034 | 22 | PA | | 26-0 | 30-11-11 | D05908P | | 16 | | | | | D05906P | 16 | | | 155 |
| 034 | 22 | PA | | 26-0 | 30-11-11 | D05656P | | 8 | | | | | D05648P | 19 | | | 275-299 |
| 036 | 22 | PA | | 26-0 | 30-11-11 | D05656P | | 11 | | | | | D05648P | 23 | | | ALL |
| 037 | 22 | PA | | 26-0 | 30-11-11 | D05656P | | 12 | | | | | D05648P | 24 | | | ALL |
| 039 | 22 | PA | | 26-0 | 30-11-11 | D05656P | | 17 | | | | | D05648P | 30 | | | ALL |
| 046 | 22 | PA | | 26-0 | 30-33-11 | D05656P | | 16 | | | | | D05648P | 49 | | | ALL |
| 064 | 22 | PA | | 26-0 | 30-34-21 | D05648P | | 44 | | | | | D05656P | 31 | | | ALL |
| 067 | 24 | PK | | 15-0 | 32-09-13 | D05290P | | 17 | | | | | D05648P | 47 | | | ALL |
| 078 | 22 | PA | | 26-0 | 30-32-11 | D05906P | | 5 | | | | | D05908P | 22 | | | ALL |
| 079 | 22 | PA | | 23-0 | 30-32-21 | SP00251 | | | 9 | | | | D05908P | 18 | | | ALL |
| 090 | 22 | PA | | 11-0 | 30-32-21 | D05906P | | 17 | | | | | SP00253 | | 9 | | ALL |
| 092 | 24 | PK | | 32-0 | 52-71-11 | D05906P | | 19 | | | | | D05496J | 6 | | | ALL |
| 093 | 18 | PA | | 20-0 | 33-31-41 | SP01658 | | | S | | | | SP00238 | | S | | ALL |
| 096 | 18 | PA | | 13-0 | 33-31-41 | SP01664 | | | S | | | | SM00001 | | S | | ALL |
| 097 | 18 | PA | | 13-0 | 33-31-41 | SP01668 | | | S | | | | SP01666 | | S | | ALL |
| 098 | 18 | PA | | 12-0 | 33-31-41 | SP01668 | | | S | | | | SP01670 | | S | | ALL |
| 099 | 18 | PA | | 18-0 | 33-31-41 | SP00240 | | | S | | | | SP01670 | | S | | ALL |
| 100 | 18 | PA | | 10-0 | 33-31-41 | SP00240 | | | S | | | | SP01672 | | S | | ALL |
| 101 | 18 | PA | | 13-0 | 33-31-41 | SP02304 | | | S | | | | SP01672 | | S | | ALL |
| 110 | 22 | PA | | 26-0 | 30-31-11 | D05906P | | 20 | | | | | D05908P | 19 | | | ALL |
| 111 | 22 | PA | | 26-0 | 30-31-13 | D05656P | | 34 | | | | | D05648P | 48 | | | ALL |
| 112 | 24 | PK | | 26-0 | 30-31-21 | D05906P | | 22 | | | | | D05908P | 20 | | | ALL |
| 113 | 24 | PK | | 26-0 | 30-31-21 | D05906P | | 21 | | | | | D05908P | 21 | | | ALL |
| 114 | 18 | PA | | 28-0 | 33-31-41 | SP01674 | | | S | | | | SM00001 | | S | | ALL |
| 116 | 18 | PA | | 12-0 | 33-31-41 | D05290P | | 14 | | | | | SP01668 | | S | | ALL |
| 117 | 18 | PA | | 3-0 | 33-31-41 | D05290P | | 16 | | | | | SM00001 | | S | | ALL |
| 118 | 20 | PA | | 16-0 | 24-51-72 | D05290P | | 1 | | | | | D05906P | 1 | | | 050-099, 162-164, 276 |
| 118 | 20 | PA | | 16-0 | SPARE | D05290P | | 1 | | | | | D05906P | 1 | | | 155-157, 165-199, 277-299 |
| 122 | 22 | PA | | 16-0 | 21-66-21 | D05290P | | 2 | | | | | D05906P | 23 | | | 050-099, 162-199 |
| 123 | 22 | PA | | 24-0 | 21-66-41 | D05290P | | 10 | | | | | D05496J | 13 | | | 050-099, 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W0900

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0902 | 286T0902 | | | FWD & MAIN EQPT CTR LTG,FWD DR WRN & CONT (continued) | | | | | | | | | | | | | |
| 124 | 22 | | PA | 16-0 | 21-66-41 | D05906P | | 30 | | | | | D05290P | 13 | | | 050-099, 162-199 |
| 125 | 22 | | PA | 32-0 | 21-66-41 | D05906P | | 31 | | | | | D05496J | 15 | | | 050-099, 162-199 |
| 126 | 22 | | PA | 24-0 | 21-66-41 | D05496J | | 14 | | | | | D05290P | 12 | | | 050-099, 150, 152-199 |
| 127 | 22 | | PA | 16-0 | 21-66-21 | D05290P | | 6 | | | | | D05906P | 32 | | | 050-099, 162-199 |
| 128 | 22 | | PA | 24-0 | 21-66-11 | D05496J | | 5 | | | | | D05290P | 15 | | | 050-099, 162-199 |
| 129 | 22 | | PA | 16-0 | 21-66-21 | D05290P | | 7 | | | | | D05906P | 24 | | | 050-099, 162-199 |
| 130 | 22 | | PA | 24-0 | 21-66-21 | D05290P | | 8 | | | | | D05496J | 8 | | | 050-099, 162-199 |
| 132 | 22 | | PA | 32-0 | 21-66-21 | D05906P | | 25 | | | | | D05496J | 7 | | | 050-099, 162-199 |
| 133 | 22 | | PA | 32-0 | 21-66-21 | D05906P | | 26 | | | | | D05496J | 9 | | | 050-099, 162-199 |
| 201B | 24 | | PL | A | 42-0 | 52-71-14 | D05496J | 2 | | | | | SP00558 | | 9 | | ALL |
| 201R | 24 | | PL | A | 0-0 | 52-71-14 | D05496J | 1 | | | | | SP00556 | | 9 | | ALL |
| 202B | 24 | | PL | B | 28-0 | 52-71-14 | D05496J | 4 | | | | | SP00562 | | 9 | | ALL |
| 202R | 24 | | PL | B | 0-0 | 52-71-14 | D05496J | 3 | | | | | SP00560 | | 9 | | ALL |
| 204B | 22 | | PR | ID | 32-0 | 21-66-21 | D05496J | 11 | | | | | D05906P | 28 | | | 050-099, 162-199 |
| 204R | 22 | | PR | ID | 0-0 | 21-66-21 | D05496J | 10 | | | | | D05906P | 27 | | | 050-099, 162-199 |
| 204Z | | | | ID | 0-0 | 21-66-21 | D05496J | 12 | | | | | D05906P | 29 | | | 050-099, 162-199 |
| 207B | 22 | | PR | IG | 24-0 | 21-66-41 | D05496J | 18 | | | | | D05290P | 23 | | | 050-099, 150, 152-199 |
| 207R | 22 | | PR | IG | 0-0 | 21-66-41 | D05496J | 17 | | | | | D05290P | 25 | | | 050-099, 150, 152-199 |
| 207Z | | | | IG | 0-0 | 21-66-41 | D05496J | 16 | | | | | D05290P | 21 | | | 050-099, 150, 152-199 |
| 814 | 20 | | PA | | 15-0 | SPARE | D05290P | 9 | | | | | D05648P | 2 | | | ALL |
| A-A | | | | | 1-0 | 33-31-41 | SP00238 | | | S | | | L00079 | P | | | ALL |
| A-B | | | | | 0-0 | 33-31-41 | L00080 | | | P | | | SP01658 | | | S | ALL |
| A-C | | | | | 0-0 | 33-31-41 | L00079 | | | G | | | GD00584 | A.. | | E | ALL |
| A-D | | | | | 0-0 | 33-31-41 | L00080 | | | G | | | GD00586 | A.. | | E | ALL |
| A-E | | | | | 0-0 | 33-31-41 | L00075 | | | G | | | GD00588 | A.. | | E | ALL |
| A-F | | | | | 0-0 | 33-31-41 | L00074 | | | P | | | SP01666 | | | S | ALL |
| A-G | | | | | 0-0 | 33-31-41 | L00075 | | | P | | | SP01664 | | | S | ALL |
| A-H | | | | | 0-0 | 33-31-41 | L00074 | | | G | | | GD00590 | A.. | | E | ALL |
| A-J | | | | | 0-0 | 33-31-41 | L00073 | | | P | | | SP01668 | | | S | ALL |
| A-K | | | | | 0-0 | 33-31-41 | L00072 | | | P | | | SP01670 | | | S | ALL |
| A-L | | | | | 0-0 | 33-31-41 | L00072 | | | G | | | GD00505 | A.. | | 2 | ALL |
| A-M | | | | | 0-0 | 33-31-41 | SP00240 | | | S | | | L00076 | P | | | ALL |
| A-N | | | | | 0-0 | 33-31-41 | L00076 | | | G | | | GD00596 | A.. | | E | ALL |
| A-P | | | | | 0-0 | 33-31-41 | L00078 | | | P | | | SP01674 | | | S | ALL |
| A-R | | | | | 0-0 | 33-31-41 | L00078 | | | G | | | GD00600 | A.. | | E | ALL |
| A-T | | | | | 0-0 | 33-31-41 | L00073 | | | G | | | GD00592 | A.. | | E | ALL |
| A-U | | | | | 0-0 | 33-31-41 | L00077 | | | BLK | | | SP01672 | | | S | ALL |
| A-V | | | | | 0-0 | 33-31-41 | L00077 | | | WHT | | | GD00598 | A.. | | E | ALL |
| A-W | | | | C | 0-0 | 52-71-14 | SP00556 | | | 9 | | | S00200 | RED | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0900
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|-------------|--|----------|---------|--------|-------|------|---------|--------|-------------|------------------|--|
| | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | | |
| W0902 | 286T0902 | | | | FWD & MAIN EQPT CTR LTG,FWD DR WRN & CONT (continued) | | | | | | | | | | |
| A-X | | | | C | 0-0 | 52-71-14 | SP00558 | | 9 | | S00200 | BLU | | ALL | |
| A-Y | | | | D | 0-0 | 52-71-14 | SP00560 | | 9 | | S00201 | RED | | ALL | |
| A-Z | | | | D | 0-0 | 52-71-14 | SP00562 | | 9 | | S00201 | BLU | | ALL | |
| B-A | | | | | 0-0 | 33-31-41 | L00672 | | P | | SP02304 | | S | ALL | |
| B-B | | | | | 0-0 | 33-31-41 | L00672 | | G | | GD04460 | A.. | E | ALL | |
| W0908 | 286T0908 | | | | TAIL-SKID CONTROL WIRE INDICATION | | | | | | | | | | |
| 201B | 22 | PB | A | A | 148-0 | 32-71-11 | D08202J | | 2 | | D08204P | | 2 | 150-199, 275-299 | |
| 201R | 22 | PB | A | A | 0-0 | 32-71-11 | D08202J | | 1 | | D08204P | | 1 | 150-199, 275-299 | |
| 202B | 22 | PB | B | B | 148-0 | 32-71-11 | D08202J | | 4 | | D08204P | | 4 | 150-199, 275-299 | |
| 202R | 22 | PB | B | B | 0-0 | 32-71-11 | D08202J | | 3 | | D08204P | | 3 | 150-199, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W0900
Page 4 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|--------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0910 | 286T0910 | | | TAIL-SKID CONTROL INDICATION SWITCHS | | | | | | | | | | | |
| 201B | 20 | UB | A | | 33-7 | 32-71-11 | D08204J | | | | SP02984 | | | | 150-199, 275-299 |
| 201R | 20 | UB | A | | 0-0 | 32-71-11 | D08204J | | | | SP02982 | | | | 150-199, 275-299 |
| 202B | 20 | UB | B | | 33-7 | 32-71-11 | D08204J | | | | SP02988 | | | | 150-199, 275-299 |
| 202R | 20 | UB | B | | 0-0 | 32-71-11 | D08204J | | | | SP02986 | | | | 150-199, 275-299 |
| A-A | | | | | 0-0 | 32-71-11 | SP02982 | | 9 | | S00247 | RED | | | 150-199, 275-299 |
| A-B | | | | | 0-0 | 32-71-11 | SP02984 | | 9 | | S00247 | BLU | | | 150-199, 275-299 |
| A-C | | | | | 0-0 | 32-71-11 | SP02986 | | 9 | | S00248 | RED | | | 150-199, 275-299 |
| A-D | | | | | 0-0 | 32-71-11 | SP02988 | | 9 | | S00248 | BLU | | | 150-199, 275-299 |
| W0916 | 286T0916 | | | WRN & CONT-CAR. DRS,OFF WG ESCAPE DRS,AFT ENTRY DRS | | | | | | | | | | | |
| 201B | 24 | PL | A | | 97-0 | 52-35-13 | D05498J | | 2 | | SP00072 | | 9 | | 050-099 |
| 201B | 24 | PL | A | | 119-11 | 52-35-13 | D05498J | | 2 | | SP00072 | | 9 | | 150-199, 275-299 |
| 201R | 24 | PL | A | | 0-0 | 52-35-13 | D05498J | | 3 | | SP00074 | | 9 | | ALL |
| 202B | 24 | PL | B | | 96-0 | 52-35-13 | D05498J | | 4 | | D08072P | | 3 | | 050-099 |
| 202B | 24 | PL | B | | 117-0 | 52-35-13 | D05498J | | 4 | | D08072P | | 3 | | 150-199, 275-299 |
| 202R | 24 | PL | B | | 0-0 | 52-35-13 | D05498J | | 5 | | D08072P | | 4 | | ALL |
| 203B | 24 | PL | C | | 96-0 | 52-35-13 | D05498J | | 6 | | D08072P | | 5 | | 050-099 |
| 203B | 24 | PL | C | | 117-0 | 52-35-13 | D05498J | | 6 | | D08072P | | 5 | | 150-199, 275-299 |
| 203R | 24 | PL | C | | 0-0 | 52-35-13 | D05498J | | 7 | | D08072P | | 6 | | ALL |
| 204B | 24 | PL | D | | 96-0 | 52-35-13 | D05498J | | 8 | | D08072P | | 7 | | 050-099 |
| 204B | 24 | PL | D | | 117-0 | 52-35-13 | D05498J | | 8 | | D08072P | | 7 | | 150-199, 275-299 |
| 204R | 24 | PL | D | | 0-0 | 52-35-13 | D05498J | | 9 | | D08072P | | 8 | | ALL |
| 205B | 24 | PL | E | | 96-0 | 52-35-13 | D05498J | | 10 | | D08072P | | 9 | | 050-099 |
| 205R | 24 | PL | E | | 0-0 | 52-35-13 | D05498J | | 11 | | D08072P | | 10 | | 050-099 |
| 206B | 24 | PL | F | | 26-0 | 52-34-13 | D05498J | | 12 | | SP00094 | | 9 | | 050-099 |
| 206B | 24 | PL | F | | 28-0 | 52-34-13 | D05498J | | 12 | | SP00094 | | 9 | | 150-199, 275-299 |
| 206R | 24 | PL | F | | 0-0 | 52-34-13 | D05498J | | 13 | | SP00096 | | 9 | | ALL |
| 207B | 24 | PL | G | | 27-0 | 52-34-13 | D05498J | | 14 | | D08070P | | 3 | | 050-099 |
| 207B | 24 | PL | G | | 29-0 | 52-34-13 | D05498J | | 14 | | D08070P | | 3 | | 150-199, 275-299 |
| 207R | 24 | PL | G | | 0-0 | 52-34-13 | D05498J | | 15 | | D08070P | | 4 | | ALL |
| 208B | 24 | PL | H | | 27-0 | 52-34-13 | D05498J | | 16 | | D08070P | | 5 | | 050-099 |
| 208B | 24 | PL | H | | 29-0 | 52-34-13 | D05498J | | 16 | | D08070P | | 5 | | 150-199, 275-299 |
| 208R | 24 | PL | H | | 0-0 | 52-34-13 | D05498J | | 17 | | D08070P | | 6 | | ALL |
| 209B | 24 | PL | J | | 27-0 | 52-71-13 | D05498J | | 25 | | D08070P | | 7 | | 050-099 |
| 209B | 24 | PL | J | | 29-0 | 52-71-13 | D05498J | | 25 | | D08070P | | 7 | | 150-199, 275-299 |
| 209R | 24 | PL | J | | 0-0 | 52-71-13 | D05498J | | 24 | | D08070P | | 8 | | ALL |
| 210B | 24 | PL | K | | 27-0 | 52-34-13 | D05498J | | 20 | | D08070P | | 9 | | 050-099 |
| 210B | 24 | PL | K | | 29-0 | 52-34-13 | D05498J | | 20 | | D08070P | | 9 | | 150-199, 275-299 |
| 210R | 24 | PL | K | | 0-0 | 52-34-13 | D05498J | | 21 | | D08070P | | 10 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0910

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | | |
|--------------|-----------------|----|-------|--|--------|----------|---------|-------|------|------|--------|---------|-------------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type | Splice |
| W0916 | 286T0916 | | | WRN & CONT-CAR. DRS,OFF WG ESCAPE DRS,AFT ENTRY DRS (continued) | | | | | | | | | | | | |
| 211B | 24 | PL | L | | 27-0 | 52-71-13 | D05498J | | 23 | | | D08070P | | 1 | | 050-099 |
| 211B | 24 | PL | L | | 29-0 | 52-71-13 | D05498J | | 23 | | | D08070P | | 1 | | 150-199, 275-299 |
| 211R | 24 | PL | L | | 0-0 | 52-71-13 | D05498J | | 22 | | | D08070P | | 2 | | ALL |
| 212B | 24 | PL | M | | 28-0 | 52-34-13 | D05498J | | 18 | | | SP00296 | | 9 | | 050-099 |
| 212B | 24 | PL | M | | 32-0 | 52-34-13 | D05498J | | 18 | | | SP00296 | | 9 | | 150-199, 275-299 |
| 212R | 24 | PL | M | | 0-0 | 52-34-13 | D05498J | | 19 | | | SP00294 | | 9 | | ALL |
| 213B | 20 | PB | N | | 102-0 | 52-71-12 | D05498J | | 27 | | | SP00300 | | 9 | | 050-099 |
| 213B | 20 | PB | N | | 113-0 | 52-71-12 | D05498J | | 27 | | | SP00300 | | 9 | | 150-199, 275-299 |
| 213R | 20 | PB | N | | 0-0 | 52-71-12 | D05498J | | 26 | | | SP00298 | | 9 | | ALL |
| 214B | 24 | PL | P | | 96-0 | 52-71-13 | D05498J | | 29 | | | D08072P | | 1 | | 050-099 |
| 214B | 24 | PL | P | | 116-0 | 52-71-13 | D05498J | | 29 | | | D08072P | | 1 | | 150-199, 275-278 |
| 214B | 24 | PL | P | | 117-0 | 52-71-13 | D05498J | | 29 | | | D08072P | | 1 | | 280-299 |
| 214R | 24 | PL | P | | 0-0 | 52-71-13 | D05498J | | 28 | | | D08072P | | 2 | | ALL |
| 215B | 24 | PL | Q | | 97-0 | 52-71-13 | D05498J | | 31 | | | SP00308 | | 9 | | 050-099 |
| 215B | 24 | PL | Q | | 119-11 | 52-71-13 | D05498J | | 31 | | | SP00308 | | 9 | | 150-199, 275-299 |
| 215R | 24 | PL | Q | | 0-0 | 52-71-13 | D05498J | | 30 | | | SP00306 | | 9 | | ALL |
| 216B | 20 | PB | R | | 116-0 | 52-71-12 | D05498J | | 33 | | | SP00312 | | 9 | | 050-099 |
| 216B | 20 | PB | R | | 127-0 | 52-71-12 | D05498J | | 33 | | | SP00312 | | 9 | | 150-199, 275-299 |
| 216R | 20 | PB | R | | 0-0 | 52-71-12 | D05498J | | 32 | | | SP00310 | | 9 | | ALL |
| 217B | 24 | PL | S | | 129-0 | 52-71-13 | D05498J | | 35 | | | SP00316 | | 9 | | 050-099 |
| 217B | 24 | PL | S | | 150-0 | 52-71-13 | D05498J | | 35 | | | SP00316 | | 9 | | 150-199, 275-299 |
| 217R | 24 | PL | S | | 0-0 | 52-71-13 | D05498J | | 34 | | | SP00314 | | 9 | | ALL |
| 218B | 20 | PB | AA | | 98-0 | 52-71-12 | D05498J | | 37 | | | SP00698 | | 9 | | 050-099 |
| 218B | 20 | PB | AA | | 113-0 | 52-71-12 | D05498J | | 37 | | | SP00698 | | 9 | | 150-199, 275-299 |
| 218R | 20 | PB | AA | | 0-0 | 52-71-12 | D05498J | | 36 | | | SP00696 | | 9 | | ALL |
| 219B | 20 | PB | AB | | 112-0 | 52-71-12 | D05498J | | 39 | | | SP00702 | | 9 | | 050-099 |
| 219B | 20 | PB | AB | | 127-0 | 52-71-12 | D05498J | | 39 | | | SP00702 | | 9 | | 150-199, 275-299 |
| 219R | 20 | PB | AB | | 0-0 | 52-71-12 | D05498J | | 38 | | | SP00700 | | 9 | | ALL |
| 231B | 24 | PW | AP | | 23-0 | 23-41-11 | D08070P | | 14 | | | SP00169 | | 9 | | 050-099 |
| 231B | 24 | PW | AP | | 24-0 | 23-41-11 | D08070P | | 14 | | | SP00169 | | 9 | | 150-199, 275-299 |
| 231R | 24 | PW | AP | | 0-0 | 23-41-11 | D08070P | | 13 | | | SP00167 | | 9 | | ALL |
| 231Z | | | AP | | 0-0 | 23-41-11 | D08070P | | 15 | | | SP00171 | | 9 | | ALL |
| 232B | 24 | PW | AQ | | 95-0 | 23-41-11 | D08072P | | 14 | | | SP00169 | | 9 | | 050-099 |
| 232B | 24 | PW | AQ | | 113-0 | 23-41-11 | D08072P | | 14 | | | SP00169 | | 9 | | 150-199, 275-299 |
| 232R | 24 | PW | AQ | | 0-0 | 23-41-11 | D08072P | | 13 | | | SP00167 | | 9 | | ALL |
| 232Z | | | AQ | | 0-0 | 23-41-11 | D08072P | | 15 | | | SP00171 | | 9 | | ALL |
| A-C | | | U | | 0-0 | 52-34-13 | SP00294 | | 9 | | | S00153 | RED | | | ALL |
| A-D | | | U | | 0-0 | 52-34-13 | SP00296 | | 9 | | | S00153 | BLU | | | ALL |
| A-E | | | V | | 0-0 | 52-71-12 | SP00298 | | 9 | | | S00219 | RED | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0910

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|--------|-------|------|------|--------|-------------|-----|
| | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | |
| W0916 | 286T0916 | | | WRN & CONT-CAR. DRS,OFF WG ESCAPE DRS,AFT ENTRY DRS (continued) | | | | | | | | | | |
| A-F | | | | V | 0-0 | 52-71-12 | SP00300 | | | | 9 | S00219 | BLU | ALL |
| A-J | | | | X | 0-0 | 52-71-13 | SP00306 | | | | 9 | S00209 | RED | ALL |
| A-K | | | | X | 0-0 | 52-71-13 | SP00308 | | | | 9 | S00209 | BLU | ALL |
| A-L | | | | Y | 0-0 | 52-71-12 | SP00310 | | | | 9 | S00218 | RED | ALL |
| A-M | | | | Y | 0-0 | 52-71-12 | SP00312 | | | | 9 | S00218 | BLU | ALL |
| A-N | | | | Z | 0-0 | 52-71-13 | SP00314 | | | | 9 | S00211 | RED | ALL |
| A-P | | | | Z | 0-0 | 52-71-13 | SP00316 | | | | 9 | S00211 | BLU | ALL |
| B-A | | | | BZ | 0-0 | 52-71-12 | SP00700 | | | | 9 | S00198 | RED | ALL |
| B-B | | | | BZ | 0-0 | 52-71-12 | SP00702 | | | | 9 | S00198 | BLU | ALL |
| B-C | | | | DZ | 0-0 | 52-35-13 | SP00072 | | | | 9 | S00158 | BLU | ALL |
| B-D | | | | DZ | 0-0 | 52-35-13 | SP00074 | | | | 9 | S00158 | RED | ALL |
| X-A | | | | CZ | 0-0 | 52-71-12 | SP00696 | | | | 9 | S00199 | RED | ALL |
| X-B | | | | CZ | 0-0 | 52-71-12 | SP00698 | | | | 9 | S00199 | BLU | ALL |
| Z-A | | | | EZ | 0-0 | 52-34-13 | SP00094 | | | | 9 | S00151 | BLU | ALL |
| Z-B | | | | EZ | 0-0 | 52-34-13 | SP00096 | | | | 9 | S00151 | RED | ALL |

WIRE LIST
D280T132

91-21-11
Section W0910
Page 3 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|----------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0920 | 286T0920 | | | R LDG GEAR DOOR SWS,SYS 2 | | | | | | | | | | | | | |
| 201B | 18 | UB | A | 5-0 | 32-61-12 | D05516P | | 2 | | | | | D01934J | 2 | | | ALL |
| 201R | 18 | UB | A | 0-0 | 32-61-12 | D05516P | | 1 | | | | | D01934J | 1 | | | ALL |
| W0922 | 286T0922 | | | L LDG GEAR DOOR SWS,SYS 1 | | | | | | | | | | | | | |
| 001 | 20 | UA | | 10-7 | 36-11-31 | D05556P | | 7 | | | | | D00418 | 6 | | | ALL |
| 002 | 20 | UA | | 10-7 | 36-11-31 | D05556P | | 3 | | | | | D00418 | 7 | | | ALL |
| 003 | 20 | UA | | 10-7 | 36-11-31 | D05556P | | 4 | | | | | D00418 | 4 | | | ALL |
| 004 | 20 | UA | | 10-7 | 36-11-31 | D05556P | | 5 | | | | | D00418 | 2 | | | ALL |
| 005 | 20 | UA | | 10-7 | 36-11-31 | D05556P | | 6 | | | | | D00418 | 1 | | | ALL |
| 006 | 20 | UA | | 10-7 | 36-11-31 | D05556P | | 8 | | | | | D00418 | 5 | | | ALL |
| 007 | 20 | UA | | 10-7 | 36-11-31 | D05556P | | 9 | | | | | D00418 | 3 | | | ALL |
| 204B | 18 | UB | A | 3-3 | 32-61-11 | D05556P | | 2 | | | | | D01946J | 2 | | | ALL |
| 204R | 18 | UB | A | 0-0 | 32-61-11 | D05556P | | 1 | | | | | D01946J | 1 | | | ALL |
| W0924 | 286T0924 | | | NOSE GEAR SWS,SYS 1 | | | | | | | | | | | | | |
| 001 | 18 | UA | | 34-0 | 33-42-11 | D05040J | | 8 | | | | | D05714P | 1 | | | ALL |
| 002 | 18 | UA | | 34-0 | 33-42-11 | D05040J | | 10 | | | | | D05714P | 2 | | | ALL |
| 003 | 10 | UA | | 3-0 | 33-42-11 | D05040J | | 9 | EO | | | | GD04214 | A.. | E | | ALL |
| 004 | 10 | UA | | 3-0 | 33-42-11 | D05040J | | 11 | EO | | | | GD04214 | A.. | E | | ALL |
| 005 | 10 | UA | | 4-0 | 33-42-11 | D05040J | | 12 | EO | | | | GD04400 | S.. | E | | ALL |
| 006 | 12 | UA | | 4-0 | 33-42-21 | D05040J | | 7 | | | | | GD04400 | S.. | E | | ALL |
| 011 | 18 | UA | | 34-0 | 33-42-21 | D05040J | | 2 | | | | | D05714P | 3 | | | ALL |
| 012 | 18 | UA | | 34-0 | 33-42-21 | D05040J | | 5 | | | | | D05714P | 4 | | | ALL |
| 013 | 14 | UA | | 3-0 | 33-42-21 | D05040J | | 1 | | | | | GD04214 | A.. | E | | ALL |
| 014 | 14 | UA | | 3-0 | 33-42-21 | D05040J | | 6 | | | | | GD04214 | A.. | E | | ALL |
| 202B | 18 | UB | B | 34-0 | 32-09-11 | D05040J | | 4 | | | | | D05576P | 4 | | | ALL |
| 202R | 18 | UB | B | 0-0 | 32-09-11 | D05040J | | 3 | | | | | D05576P | 3 | | | ALL |
| 203B | 18 | UB | C | 23-0 | 32-61-13 | D05576P | | 6 | | | | | D02226J | 2 | | | ALL |
| 203R | 18 | UB | C | 0-0 | 32-61-13 | D05576P | | 5 | | | | | D02226J | 1 | | | ALL |
| 204B | 18 | UB | D | 34-0 | 32-61-13 | D05576P | | 8 | | | | | D01958J | 2 | | | ALL |
| 204R | 18 | UB | D | 0-0 | 32-61-13 | D05576P | | 7 | | | | | D01958J | 1 | | | ALL |
| 205B | 18 | UB | E | 34-0 | 32-61-13 | D05576P | | 10 | | | | | D01956J | 2 | | | ALL |
| 205R | 18 | UB | E | 0-0 | 32-61-13 | D05576P | | 9 | | | | | D01956J | 1 | | | ALL |
| 206B | 18 | UB | F | 23-0 | 32-61-13 | D05576P | | 12 | | | | | D01960J | 2 | | | ALL |
| 206R | 18 | UB | F | 0-0 | 32-61-13 | D05576P | | 11 | | | | | D01960J | 1 | | | ALL |
| W0926 | 286T0926 | | | NOSE GEAR SWS,SYS 2 | | | | | | | | | | | | | |
| 009 | 18 | UA | | 21-0 | 33-31-11 | D05592P | | 9 | | | | | L00055 | = P | L | * | ALL |

WIRE LIST

D280T132

91-21-11

Section W0920

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0926 | 286T0926 | | | NOSE GEAR SWS,SYS 2 (continued) | | | | | | | | | | | |
| 010 | 18 | | UA | | 41-0 | 33-31-11 | L00054 | =P | L | | L00055 | =P | L | * | ALL |
| 011 | 18 | | UA | | 5-0 | 33-31-11 | L00054 | =G | N | | GD01326 | A.. | N | | ALL |
| 012 | 18 | | UA | | 19-0 | 33-31-11 | L00055 | =G | N | | GD00674 | A.. | 2 | | ALL |
| 013 | 20 | | UA | | 19-0 | 23-43-11 | D05850J | | 1 | | D05852J | | 1 | | ALL |
| 014 | 20 | | UA | | 19-0 | 23-43-11 | D05850J | | 2 | | D05852J | | 2 | | ALL |
| 015 | 20 | | UA | | 16-0 | 33-51-21 | D05850J | | 9 | | D05592P | | 10 | | ALL |
| 016 | 20 | | UA | | 16-0 | 33-51-21 | D05850J | | 10 | | D05592P | | 11 | | ALL |
| 017 | 20 | | UA | | 4-0 | 33-51-21 | D05850J | | 11 | | GD00674 | D.. | 2 | | ALL |
| 018 | 18 | | UA | | 16-0 | 33-31-11 | D05850J | | 12 | | D05592P | | 12 | | ALL |
| 019 | 18 | | UA | | 16-0 | 33-31-11 | D05850J | | 13 | | D05592P | | 13 | | ALL |
| 201B | 18 | | UB | A | 16-0 | 32-61-13 | D05592P | | 2 | | D01952J | | 2 | | ALL |
| 201R | 18 | | UB | A | 0-0 | 32-61-13 | D05592P | | 1 | | D01952J | | 1 | | ALL |
| 202B | 18 | | UB | B | 16-0 | 32-61-13 | D05592P | | 4 | | D01950J | | 2 | | ALL |
| 202R | 18 | | UB | B | 0-0 | 32-61-13 | D05592P | | 3 | | D01950J | | 1 | | ALL |
| 203B | 18 | | UB | C | 28-0 | 32-61-13 | D05592P | | 6 | | D01954J | | 2 | | ALL |
| 203R | 18 | | UB | C | 0-0 | 32-61-13 | D05592P | | 5 | | D01954J | | 1 | | ALL |
| 204B | 18 | | UB | D | 25-0 | 32-61-13 | D05592P | | 8 | | D02224J | | 2 | | ALL |
| 204R | 18 | | UB | D | 0-0 | 32-61-13 | D05592P | | 7 | | D02224J | | 1 | | ALL |
| 205B | 20 | | VG | E | 19-0 | 23-41-11 | D05850J | | 3 | | D05852J | | 3 | | ALL |
| 205R | 20 | | VG | E | 0-0 | 23-41-11 | D05850J | | 4 | | D05852J | | 4 | | ALL |
| 205Z | | | | E | 0-0 | 23-41-11 | D05850J | | 5 | | D05852J | | 5 | | ALL |
| 206B | 20 | | VG | F | 19-0 | 23-51-11 | D05850J | | 6 | | D05852J | | 6 | | ALL |
| 206R | 20 | | VG | F | 0-0 | 23-51-11 | D05850J | | 7 | | D05852J | | 7 | | ALL |
| 206Z | | | | F | 0-0 | 23-51-11 | D05850J | | 8 | | D05852J | | 8 | | ALL |
| 207B | 20 | | UB | G | 16-0 | 32-09-12 | D05850J | | 16 | | D05592P | | 16 | | ALL |
| 207R | 20 | | UB | G | 0-0 | 32-09-12 | D05850J | | 15 | | D05592P | | 15 | | ALL |
| 208B | 20 | | PR | H | 16-0 | 32-45-12 | D05592P | | 17 | | D05850J | | 17 | | ALL |
| 208R | 20 | | PR | H | 0-0 | 32-45-12 | D05592P | | 18 | | D05850J | | 18 | | ALL |
| 208Z | | | | H | 0-0 | 32-45-12 | D05592P | | 14 | | D05850J | | 14 | | ALL |
| W0928 | 286T0928 | | | RIGHT MAIN GEAR UPPER J-BOX-SYS 1 | | | | | | | | | | | |
| 201B | 18 | | UB | A | 18-0 | 32-61-12 | D04300P | | 2 | | D05034P | | 2 | | ALL |
| 201R | 18 | | UB | A | 0-0 | 32-61-12 | D04300P | | 1 | | D05034P | | 1 | | ALL |
| 202B | 18 | | UB | B | 18-0 | 32-61-12 | D04300P | | 4 | | D05034P | | 4 | | ALL |
| 202R | 18 | | UB | B | 0-0 | 32-61-12 | D04300P | | 3 | | D05034P | | 3 | | ALL |
| 203B | 18 | | UB | C | 18-0 | 32-09-11 | D04300P | | 6 | | D05034P | | 6 | | ALL |
| 203R | 18 | | UB | C | 0-0 | 32-09-11 | D04300P | | 5 | | D05034P | | 5 | | ALL |
| 204B | 20 | | VG | D | 18-0 | 32-42-11 | D04300P | | 8 | | D05034P | | 8 | | ALL |
| 204R | 20 | | VG | D | 0-0 | 32-42-11 | D04300P | | 7 | | D05034P | | 7 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W0920
Page 2
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0928 | 286T0928 | | | RIGHT MAIN GEAR UPPER J-BOX-SYS 1 (continued) | | | | | | | | | | | |
| 204Z | | | D | 0-0 | 32-42-11 | D04300P | | 17 | | | D05034P | | 15 | | ALL |
| 205B | 20 | VG | E | 18-0 | 32-42-11 | D04300P | | 10 | | | D05034P | | 10 | | ALL |
| 205R | 20 | VG | E | 0-0 | 32-42-11 | D04300P | | 9 | | | D05034P | | 9 | | ALL |
| 205Z | | | E | 0-0 | 32-42-11 | D04300P | | 19 | | | D05034P | | 16 | | ALL |
| 207B | 20 | VG | K | 20-0 | 32-45-14 | D08272P | | 8 | | | D05034P | | 25 | | 050-099, 155-199, 275-299 |
| 207B | 20 | VG | K | 20-0 | 32-45-14 | D08272P | | 8 | | | D05034P | CAP | Y | | 150-154 |
| 207R | 20 | VG | K | 0-0 | 32-45-14 | D08272P | | 9 | | | D05034P | | 26 | | 050-099, 155-199, 275-299 |
| 207R | 20 | VG | K | 0-0 | 32-45-14 | D08272P | | 9 | | | D05034P | CAP | Y | | 150-154 |
| 207Z | | | K | 0-0 | 32-45-14 | D08272P | | 10 | | | D05034P | | 27 | | 050-099, 155-199, 275-299 |
| 207Z | | | K | 0-0 | 32-45-14 | D08272P | | 10 | | | D05034P | DED | | | 150-154 |
| 208B | 20 | VG | L | 20-0 | 32-45-14 | D08272P | | 11 | | | D05034P | | 28 | | 050-099, 155-199, 275-299 |
| 208B | 20 | VG | L | 20-0 | 32-45-14 | D08272P | | 11 | | | D05034P | CAP | Y | | 150-154 |
| 208R | 20 | VG | L | 0-0 | 32-45-14 | D08272P | | 12 | | | D05034P | | 29 | | 050-099, 155-199, 275-299 |
| 208R | 20 | VG | L | 0-0 | 32-45-14 | D08272P | | 12 | | | D05034P | CAP | Y | | 150-154 |
| 208Z | | | L | 0-0 | 32-45-14 | D08272P | | 13 | | | D05034P | | 30 | | 050-099, 155-199, 275-299 |
| 208Z | | | L | 0-0 | 32-45-14 | D08272P | | 13 | | | D05034P | DED | | | 150-154 |
| 451G | 18 | UY | F | 18-0 | 32-46-11 | D04300P | | 12 | 4G | | D05034P | | 12 | 4H | ALL |
| 451W | 18 | UY | F | 0-0 | 32-46-11 | D04300P | | 11 | 4K | | D05034P | | 11 | 4L | ALL |
| 452G | 18 | UY | G | 18-0 | 32-46-11 | D04300P | | 14 | 4G | | D05034P | | 14 | 4H | ALL |
| 452W | 18 | UY | G | 0-0 | 32-46-11 | D04300P | | 13 | 4K | | D05034P | | 13 | 4L | ALL |

WIRE LIST

D280T132

91-21-11

Section W0920

Page 3 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|---|-------|-------------|-------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0930 | 286T0930 | L WW LTS & LDG GEAR DOOR SWS | | | | | | | | | | | | | |
| 001 | 16 | | UA | | 4-0 | 33-31-11 | L00056 | =G | N | * | L00057 | =G | N | | 050-099 |
| 001 | 16 | | UA | | 3-7 | 33-31-11 | L00056 | =G | N | * | L00057 | =G | N | | 150-199, 275-299 |
| 002 | 16 | | UA | | 4-0 | 33-31-11 | L00056 | =P | L | * | L00057 | =P | L | | 050-099 |
| 002 | 16 | | UA | | 3-7 | 33-31-11 | L00056 | =P | L | * | L00057 | =P | L | | 150-199, 275-299 |
| 005 | 16 | | UA | | 5-0 | 33-31-11 | D04654P | | | | L00056 | =P | L | | 050-099 |
| 005 | 16 | | UA | | 4-9 | 33-31-11 | D04654P | | | | L00056 | =P | L | * | 150-199, 275-299 |
| 006 | 16 | | UA | | 5-0 | 33-31-11 | L00056 | =G | N | * | D04654P | | | | 050-099 |
| 006 | 16 | | UA | | 4-9 | 33-31-11 | L00056 | =G | N | * | D04654P | | | | 150-199, 275-299 |
| 007 | 20 | | UA | | 18-0 | 33-31-11 | D04654P | | | | S00468 | 3 | L | | 050-099 |
| 007 | 20 | | UA | | 16-11 | 33-31-11 | D04654P | | | | S00468 | 3 | L | | 150-199, 275-299 |
| 008 | 20 | | UA | | 18-0 | 33-31-11 | D04654P | | | | S00468 | 1 | L | | 050-099 |
| 008 | 20 | | UA | | 16-11 | 33-31-11 | D04654P | | | | S00468 | 1 | L | | 150-199, 275-299 |
| 010 | 20 | | UA | | 18-0 | 33-31-11 | D04654P | | | | S00468 | 2 | L | | 050-099 |
| 010 | 20 | | UA | | 16-11 | 33-31-11 | D04654P | | | | S00468 | 2 | L | | 150-199, 275-299 |
| 201B | 18 | | UB | A | 5-0 | 32-61-11 | D04654P | | | | D01938J | 2 | | | 050-099 |
| 201B | 18 | | UB | A | 4-2 | 32-61-11 | D04654P | | | | D01938J | 2 | | | 150-199, 275-299 |
| 201R | 18 | | UB | A | 0-0 | 32-61-11 | D04654P | | | | D01938J | 1 | | | ALL |
| W0932 | 286T0932 | R WW LTS & LDG GEAR DR SWS | | | | | | | | | | | | | |
| 003 | 16 | | UA | | 7-0 | 33-31-11 | L00118 | =P | G7 | * | L00117 | =P | G7 | | 050-099 |
| 003 | 16 | | UA | | 4-2 | 33-31-11 | L00118 | =P | G7 | * | L00117 | =P | G7 | | 150-199, 275-299 |
| 004 | 16 | | UA | | 7-0 | 33-31-11 | L00118 | =G | N | * | L00117 | =G | N | | 050-099 |
| 004 | 16 | | UA | | 4-2 | 33-31-11 | L00118 | =G | N | * | L00117 | =G | N | | 150-199, 275-299 |
| 005 | 20 | | UA | | 16-0 | 33-31-11 | D05608P | | | | D05810P | 4 | | | 050-099 |
| 005 | 20 | | UA | | 15-2 | 33-31-11 | D05608P | | | | D05810P | 4 | | | 150-199, 275-299 |
| 006 | 16 | | UA | | 5-0 | 33-31-11 | L00118 | =G | N | * | D05608P | 6 | | | 050-099 |
| 006 | 16 | | UA | | 3-10 | 33-31-11 | L00118 | =G | N | * | D05608P | 6 | | | 150-199, 275-299 |
| 007 | 16 | | UA | | 5-0 | 33-31-11 | D05608P | | | | L00118 | =P | G7 | * | 050-099 |
| 007 | 16 | | UA | | 3-10 | 33-31-11 | D05608P | | | | L00118 | =P | G7 | * | 150-199, 275-299 |
| 008 | 20 | | UA | | 16-0 | 33-31-11 | D05608P | | | | D05810P | 5 | | | 050-099 |
| 008 | 20 | | UA | | 15-2 | 33-31-11 | D05608P | | | | D05810P | 5 | | | 150-199, 275-299 |
| 009 | 20 | | UA | | 16-0 | 33-31-11 | D05608P | | | | D05810P | 6 | | | 050-099 |
| 009 | 20 | | UA | | 15-2 | 33-31-11 | D05608P | | | | D05810P | 6 | | | 150-199, 275-299 |
| 201B | 18 | | UB | A | 5-0 | 32-61-12 | D05608P | | | | D01942J | 2 | | | 050-099 |
| 201B | 18 | | UB | A | 4-3 | 32-61-12 | D05608P | | | | D01942J | 2 | | | 150-199, 275-299 |
| 201R | 18 | | UB | A | 0-0 | 32-61-12 | D05608P | | | | D01942J | 1 | | | ALL |
| 203B | 20 | | VG | C | 17-0 | 23-41-11 | D05810P | | | | D05409P | 2 | | | 050-099 |
| 203B | 20 | | VG | C | 15-1 | 23-41-11 | D05810P | | | | D05409P | 2 | | | 150-199, 275-299 |
| 203R | 20 | | VG | C | 0-0 | 23-41-11 | D05810P | | | | D05409P | 1 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0930

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0932 | 286T0932 | | | | R WW LTS & LDG GEAR DR SWS (continued) | | | | | | | | | | | |
| 203Z | | | | C | 0-0 | 23-41-11 | D05810P | | 3 | | D05409P | | 3 | | | ALL |
| W0934 | 286T0934 | | | | AFT CARGO TEMP CONTROL SWITCH | | | | | | | | | | | |
| 001 | 24 | | PK | | 10-0 | 21-44-11 | D05950P | | 1 | | D00648 | | 1 | | | ALL |
| 002 | 24 | | PK | | 10-0 | 21-44-11 | D05948P | | 1 | | D00708 | | 1 | | | ALL |
| 003 | 20 | | PA | | 10-0 | 21-44-11 | D00708 | | 2 | | GD01138 | | D.. | E | | ALL |
| 004 | 20 | | PA | | 10-0 | 21-44-11 | D00648 | | 2 | | GD01138 | | D.. | E | | ALL |
| W0938 | 286T0938 | | | | L TURB BYP VALVE, RAM ATR INLET, EXIT ACTR, & M00571 IN WHEEL WELL | | | | | | | | | | | |
| 001 | 20 | | UA | | 32-0 | 21-53-11 | D08044P | | 1 | | D00682 | | 3 | | | ALL |
| 002 | 20 | | UA | | 32-0 | 21-53-11 | D08044P | | 2 | | D00682 | | 2 | | | ALL |
| 003 | 20 | | UA | | 19-0 | 21-53-11 | D08044P | | 3 | | D00674 | | 3 | | | ALL |
| 004 | 20 | | UA | | 19-0 | 21-53-11 | D08044P | | 8 | | D00674 | | 2 | | | ALL |
| 005 | 20 | | UA | | 24-0 | 21-53-11 | D08044P | | 5 | | D00676 | | 1 | | | ALL |
| 006 | 20 | | UA | | 24-0 | 21-53-11 | D08044P | | 6 | | D00676 | | 2 | | | ALL |
| 007 | 18 | | UA | | 4-9 | 21-53-11 | D00676 | | 3 | DK | GD00856 | | A.. | N | | ALL |
| 008 | 18 | | UA | | 7-0 | 21-53-11 | D00682 | | 1 | DK | GD00858 | | A.. | N | | ALL |
| 009 | 18 | | UA | | 4-0 | 21-53-11 | D00674 | | 1 | DK | GD00860 | | A.. | N | | ALL |
| 010 | 20 | | UA | | 24-0 | 21-53-12 | D00676 | | 6 | | D08046P | | 1 | | | ALL |
| 011 | 18 | | UA | | 6-0 | 21-53-12 | D00676 | | 8 | DK | GD00864 | | D.. | N | | ALL |
| 012 | 20 | | UA | | 24-0 | 21-53-12 | D00676 | | 9 | | D08046P | | 2 | | | ALL |
| 013 | 18 | | UA | | 6-0 | 21-53-12 | D00676 | | 11 | DK | GD00864 | | D.. | N | | ALL |
| 014 | 18 | | UA | | 6-0 | 21-53-12 | D00676 | | 13 | DK | GD00814 | | S.. | N | | ALL |
| 015 | 20 | | UA | | 19-0 | 21-53-12 | D00674 | | 13 | | D08046P | | 3 | | | 050-099, 153-199, 275-299 |
| 015 | 20 | | UA | | 18-0 | 21-53-12 | D00674 | | 13 | | D08046P | | 3 | | | 150-152 |
| 016 | 18 | | UA | | 4-0 | 21-53-12 | D00674 | | 15 | DK | GD00868 | | D.. | N | | ALL |
| 017 | 20 | | UA | | 19-0 | 21-53-12 | D00674 | | 16 | | D08046P | | 4 | | | 050-099, 153-199, 275-299 |
| 017 | 20 | | UA | | 18-0 | 21-53-12 | D00674 | | 16 | | D08046P | | 4 | | | 150-152 |
| 018 | 18 | | UA | | 4-0 | 21-53-12 | D00674 | | 18 | DK | GD00868 | | D.. | N | | ALL |
| 019 | 18 | | UA | | 4-0 | 21-53-12 | D00674 | | 19 | DK | GD00870 | | S.. | N | | ALL |
| 020 | 20 | | UA | | 32-0 | 21-53-12 | D00682 | | 13 | | D08046P | | 5 | | | ALL |
| 021 | 18 | | UA | | 8-0 | 21-53-12 | D00682 | | 15 | DK | GD00872 | | D.. | N | | ALL |
| 022 | 20 | | UA | | 32-0 | 21-53-12 | D00682 | | 16 | | D08046P | | 6 | | | ALL |
| 023 | 18 | | UA | | 8-0 | 21-53-12 | D00682 | | 18 | DK | GD00872 | | D.. | N | | ALL |
| 024 | 18 | | UA | | 7-0 | 21-53-12 | D00682 | | 19 | DK | GD00874 | | S.. | N | | ALL |
| 025 | 18 | | UA | | 19-0 | 33-31-21 | D08044P | | 4 | | SM00001 | | | 9 | | ALL |
| 026 | 18 | | UA | | 22-0 | 33-31-21 | D08044P | | 10 | | D03062 | | 3 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0930

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0938 | 286T0938 | | | L TURB BYP VALVE, RAM ATR INLET, EXIT ACTR, & M00571 IN WHEEL WELL (continued) | | | | | | | | | | | | | |
| 027 | 18 | | UA | 3-0 | 33-31-21 | D03062 | | 5 | | | | | SM00001 | | 9 | | ALL |
| 028 | 18 | | UA | 4-0 | 33-31-21 | D03062 | | 1 | | | | | GD01278 | A.. | N | | ALL |
| 029 | 18 | | UA | 3-0 | 33-31-21 | D03062 | | 6 | | | | | GD01292 | S.. | N | | ALL |
| 030 | 18 | | UA | 2-0 | 33-31-21 | SM00001 | | | 9 | | | | S00361 | 2 | L | | ALL |
| 031 | 18 | | UA | 4-0 | 33-31-21 | S00361 | | 3 | L | | | | SP00514 | | 9 | | ALL |
| 032 | 18 | | UA | 15-0 | 33-31-21 | SP00514 | | | 9 | | | | SP00512 | | 9 | | ALL |
| 033 | 20 | | UA | 23-0 | 21-61-51 | D00702 | | 1 | | | | | D08046P | | 7 | | ALL |
| 034 | 18 | | UA | 5-0 | 21-61-51 | D00702 | | 2 | DK | | | | GD02018 | S.. | N | | ALL |
| 035 | 18 | | UA | 6-0 | 21-61-51 | D00702 | | 3 | DK | | | | GD02016 | D.. | N | | ALL |
| 037 | 20 | | UA | 36-0 | 36-11-11 | D08042P | | 19 | | | | | D01162 | | 1 | | ALL |
| 038 | 20 | | UA | 36-0 | 36-11-11 | D08042P | | 20 | | | | | D01162 | | 2 | | ALL |
| 039 | 20 | | UA | 36-0 | 36-11-11 | D08042P | | 21 | | | | | D01162 | | 4 | | ALL |
| 040 | 20 | | UA | 36-0 | 36-11-11 | D08042P | | 22 | | | | | D01162 | | 7 | | ALL |
| 041 | 18 | | UA | 3-0 | 36-11-11 | D01162 | | 5 | | | | | GD02378 | D.. | N | | ALL |
| 042 | 18 | | UA | 3-0 | 36-11-11 | D01162 | | 6 | | | | | GD02378 | D.. | N | | ALL |
| 043 | 18 | | UA | 3-0 | 36-11-11 | D01162 | | 3 | | | | | GD02380 | A.. | N | | ALL |
| 051 | 18 | | UA | 35-0 | 33-44-11 | D02666 | | 1 | | | | | D08046P | | 9 | DL | 050-099, 153-199, 275-299 |
| 051 | 20 | | UA | 24-0 | 33-44-11 | SM00002 | | | 9 | | | | D08046P | | 9 | | 150-152 |
| 052 | 16 | | UA | 13-0 | 33-44-11 | D02666 | | 2 | | | | | GD00682 | A.. | N | | 050-099, 153-199, 275-299 |
| 052 | 16 | | UA | 19-0 | 33-44-11 | D02666 | | 2 | | | | | GD00682 | A.. | E | | 150-152 |
| 053 | 16 | | UA | 13-0 | 33-44-11 | D02666 | | 3 | | | | | GD00680 | S.. | N | | 050-099, 153-199, 275-299 |
| 053 | 16 | | UA | 19-0 | 33-44-11 | D02666 | | 3 | | | | | GD00680 | S.. | E | | 150-152 |
| 054R | 18 | | XG | 32-0 | 26-18-11 | D08042P | | 28 | DL | | | | D01800 | =1 | | | ALL |
| 067 | 18 | | 5A | 15-0 | 33-44-11 | SM00002 | | | 9 | | | | D02666 | | 1 | | 150-152 |
| 201B | 20 | | UB | H | 19-0 | 21-51-13 | D08046P | | 13 | | | | D10134 | | 1 | | ALL |
| 201R | 20 | | UB | H | 0-0 | 21-51-13 | D08046P | | 14 | | | | D10134 | | 2 | | ALL |
| 202B | 20 | | UB | I | 24-0 | 21-51-13 | D08046P | | 15 | | | | D10136 | | 1 | | ALL |
| 202R | 20 | | UB | I | 0-0 | 21-51-13 | D08046P | | 16 | | | | D10136 | | 2 | | ALL |
| 301B | 20 | | UC | A | 24-0 | 21-53-11 | D08042P | | 1 | | | | D00676 | | 5 | | ALL |
| 301R | 20 | | UC | A | 0-0 | 21-53-11 | D08042P | | 2 | | | | D00676 | | 4 | | ALL |
| 301Y | 20 | | UC | A | 0-0 | 21-53-11 | D08042P | | 3 | | | | D00676 | | 12 | | ALL |
| 302B | 20 | | UC | B | 30-0 | 21-53-11 | D08042P | | 4 | | | | D00682 | | 10 | | 050-099, 153-199, 275-299 |
| 302B | 20 | | UC | B | 32-0 | 21-53-11 | D08042P | | 4 | | | | D00682 | | 10 | | 150-152 |
| 302R | 20 | | UC | B | 0-0 | 21-53-11 | D08042P | | 5 | | | | D00682 | | 11 | | ALL |
| 302Y | 20 | | UC | B | 0-0 | 21-53-11 | D08042P | | 6 | | | | D00682 | | 12 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0930

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|------|---|---------|-------|------|------|--------|---------|------|-------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0938 | 286T0938 | | | | L TURB BYP VALVE, RAM ATR INLET, EXIT ACTR, & M00571 IN WHEEL WELL (continued) | | | | | | | | | | |
| 303B | 20 | UC | C | 19-0 | 21-53-11 | D08042P | | 7 | | D00674 | | 10 | | 050-099, 153-199, 275-299 | |
| 303B | 20 | UC | C | 18-0 | 21-53-11 | D08042P | | 7 | | D00674 | | 10 | | 150-152 | |
| 303R | 20 | UC | C | 0-0 | 21-53-11 | D08042P | | 8 | | D00674 | | 11 | | ALL | |
| 303Y | 20 | UC | C | 0-0 | 21-53-11 | D08042P | | 9 | | D00674 | | 12 | | ALL | |
| 304B | 20 | UC | D | 19-0 | 21-52-11 | D08042P | | 10 | | D00674 | | 7 | | 050-099, 153-199, 275-299 | |
| 304B | 20 | UC | D | 18-0 | 21-52-11 | D08042P | | 10 | | D00674 | | 7 | | 150-152 | |
| 304R | 20 | UC | D | 0-0 | 21-52-11 | D08042P | | 11 | | D00674 | | 8 | | ALL | |
| 304Y | 20 | UC | D | 0-0 | 21-52-11 | D08042P | | 12 | | D00674 | | 9 | | ALL | |
| 305B | 20 | UC | E | 19-0 | 21-51-12 | D08042P | | 13 | | D00674 | | 6 | | 050-099, 153-199, 275-299 | |
| 305B | 20 | UC | E | 18-0 | 21-51-12 | D08042P | | 13 | | D00674 | | 6 | | 150-152 | |
| 305R | 20 | UC | E | 0-0 | 21-51-12 | D08042P | | 14 | | D00674 | | 5 | | ALL | |
| 305Y | 20 | UC | E | 0-0 | 21-51-12 | D08042P | | 15 | | D00674 | | 4 | | ALL | |
| 306B | 20 | UC | F | 30-0 | 21-51-12 | D08042P | | 16 | | D00682 | | 6 | | 050-099, 153-199, 275-299 | |
| 306B | 20 | UC | F | 32-0 | 21-51-12 | D08042P | | 16 | | D00682 | | 6 | | 150-152 | |
| 306R | 20 | UC | F | 0-0 | 21-51-12 | D08042P | | 17 | | D00682 | | 5 | | ALL | |
| 306Y | 20 | UC | F | 0-0 | 21-51-12 | D08042P | | 18 | | D00682 | | 4 | | ALL | |
| 307B | 20 | UC | MG | 30-0 | 21-52-11 | D08042P | | 29 | | D00682 | | 7 | | 050-099, 275-299 | |
| 307B | 20 | UC | MG | 32-0 | 21-52-11 | D08042P | | 29 | | D00682 | | 7 | | 150-152 | |
| 307B | 20 | UC | MG | 31-0 | 21-52-11 | D08042P | | 29 | | D00682 | | 7 | | 153-199 | |
| 307R | 20 | UC | MG | 0-0 | 21-52-11 | D08042P | | 30 | | D00682 | | 8 | | ALL | |
| 307Y | 20 | UC | MG | 0-0 | 21-52-11 | D08042P | | 31 | | D00682 | | 9 | | ALL | |
| A-A | | | | 0-0 | 33-31-21 | SP00512 | | | 9 | | L00132 | | BLK | ALL | |
| A-B | | | | 0-0 | 33-31-21 | L00132 | | | WHT | | GD01276 | | A.. N | ALL | |
| A-C | | | | 0-0 | 33-31-21 | SP00514 | | | 9 | | L00131 | | BLK | ALL | |
| A-D | | | | 0-0 | 33-31-21 | L00131 | | | WHT | | GD01278 | | A.. N | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0930

Page 4 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID | | | | | | | | | | | |
| 002 | 24 | | PK | | 50-0 | 21-51-11 | D04904P | | | | D05048J | | | | 050-099 |
| 002 | 24 | | PK | | 59-0 | 21-51-11 | D04904P | | | | D05048J | | | | 150-199, 275-299 |
| 003 | 24 | | PK | | 22-7 | 21-58-11 | D08112P | | | 32 | D08004J | | | 21 | ALL |
| 005 | 22 | | PA | | 71-0 | 32-42-11 | D04908J | | | | D05562J | | | | 050-099 |
| 005 | 22 | | PA | | 81-0 | 32-42-11 | D04908J | | | | D05562J | | | | 150-199, 275-299 |
| 006 | 20 | | PA | | 4-0 | 32-42-11 | GD00792 | | D.. | 2 | D05562J | | | | 050-099 |
| 006 | 20 | | PA | | 5-0 | 32-42-11 | GD00792 | | D.. | 2 | D05562J | | | | 150-199, 275-299 |
| 007 | 22 | | PA | | 71-0 | 32-42-11 | D04908J | | | | D05562J | | | | 050-099 |
| 007 | 22 | | PA | | 81-0 | 32-42-11 | D04908J | | | | D05562J | | | | 150-199, 275-299 |
| 008 | 20 | | PA | | 4-0 | 32-42-11 | GD00792 | | D.. | 2 | D05562J | | | | 050-099 |
| 008 | 20 | | PA | | 5-0 | 32-42-11 | GD00792 | | D.. | 2 | D05562J | | | | 150-199, 275-299 |
| 009 | 22 | | PA | | 71-0 | 32-42-11 | D04908J | | | | D05562J | | | | 050-099 |
| 009 | 22 | | PA | | 81-0 | 32-42-11 | D04908J | | | | D05562J | | | | 150-199, 275-299 |
| 010 | 20 | | PA | | 4-0 | 32-42-11 | GD00792 | | D.. | 2 | D05562J | | | | 050-099 |
| 010 | 20 | | PA | | 5-0 | 32-42-11 | GD00792 | | D.. | 2 | D05562J | | | | 150-199, 275-299 |
| 011 | 24 | | PK | | 50-0 | 28-22-12 | D04906P | | | | D06658P | | | | 050-099, 275-299 |
| 015 | 24 | | PK | | 14-0 | 21-58-13 | D04904P | | | | D08004J | | | | ALL |
| 016 | 20 | | PQ | Q | 79-0 | 28-41-21 | D04466J | | | | D05562J | | | | 050-099 |
| 016 | 20 | | PQ | Q | 93-0 | 28-41-21 | D04466J | | | | D05562J | | | | 150-199, 275-299 |
| 016Z | | | | Q | 0-0 | 28-41-21 | D04466J | | = C1 | | D05562J | | = C1 | | ALL |
| 017 | 24 | | PK | | 80-0 | 28-41-21 | D04448J | | | | D04594J | | | | 050-099 |
| 017 | 24 | | PK | | 91-0 | 28-41-21 | D04448J | | | | D04594J | | | | 150-199, 275-299 |
| 018 | 24 | | PK | | 80-0 | 28-41-21 | D04448J | | | | D04594J | | | | 050-099 |
| 018 | 24 | | PK | | 91-0 | 28-41-21 | D04448J | | | | D04594J | | | | 150-199, 275-299 |
| 019 | 24 | | PK | | 80-0 | 28-41-21 | D04448J | | | | D04594J | | | | 050-099 |
| 019 | 24 | | PK | | 91-0 | 28-41-21 | D04448J | | | | D04594J | | | | 150-199, 275-299 |
| 020 | 24 | | PK | | 80-0 | 28-41-21 | D04448J | | | | D04594J | | | | 050-099 |
| 020 | 24 | | PK | | 91-0 | 28-41-21 | D04448J | | | | D04594J | | | | 150-199, 275-299 |
| 021 | 24 | | PK | | 80-0 | 28-41-21 | D04448J | | | | D04594J | | | | 050-099 |
| 021 | 24 | | PK | | 91-0 | 28-41-21 | D04448J | | | | D04594J | | | | 150-199, 275-299 |
| 022 | 24 | | PK | | 80-0 | 28-41-21 | D04448J | | | | D04594J | | | | 050-099 |
| 022 | 24 | | PK | | 91-0 | 28-41-21 | D04448J | | | | D04594J | | | | 150-199, 275-299 |
| 023 | 24 | | PK | | 80-0 | 28-41-21 | D04448J | | | | D04594J | | | | 050-099 |
| 023 | 24 | | PK | | 91-0 | 28-41-21 | D04448J | | | | D04594J | | | | 150-199, 275-299 |
| 024 | 24 | | PK | | 80-0 | 28-41-21 | D04448J | | | | D04594J | | | | 050-099 |
| 024 | 24 | | PK | | 91-0 | 28-41-21 | D04448J | | | | D04594J | | | | 150-199, 275-299 |
| 025 | 24 | | PK | | 80-0 | 28-41-21 | D04448J | | | | D04594J | | | | 050-099 |
| 025 | 24 | | PK | | 91-0 | 28-41-21 | D04448J | | | | D04594J | | | | 150-199, 275-299 |
| 026 | 24 | | PK | | 80-0 | 28-41-21 | D04448J | | | | D04594J | | | | 050-099 |

WIRE LIST

D280T132

91-21-11
 Section W0940
 Page 1
 Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | | | |
| 026 | 24 | | PK | 91-0 | 28-41-21 | D04448J | | 10 | | | | | D04594J | 10 | | | 150-199, 275-299 |
| 027 | 24 | | PK | 80-0 | 28-41-21 | D04448J | | 11 | | | | | D04594J | 11 | | | 050-099 |
| 027 | 24 | | PK | 91-0 | 28-41-21 | D04448J | | 11 | | | | | D04594J | 11 | | | 150-199, 275-299 |
| 028 | 24 | | PK | 80-0 | 28-41-21 | D04448J | | 12 | | | | | D04594J | 12 | | | 050-099 |
| 028 | 24 | | PK | 91-0 | 28-41-21 | D04448J | | 12 | | | | | D04594J | 12 | | | 150-199, 275-299 |
| 029 | 24 | | PK | 80-0 | 28-41-21 | D04448J | | 13 | | | | | D04594J | 13 | | | 050-099 |
| 029 | 24 | | PK | 91-0 | 28-41-21 | D04448J | | 13 | | | | | D04594J | 13 | | | 150-199, 275-299 |
| 030 | 24 | | PK | 80-0 | 28-41-21 | D04448J | | 14 | | | | | D04594J | 14 | | | 050-099 |
| 030 | 24 | | PK | 91-0 | 28-41-21 | D04448J | | 14 | | | | | D04594J | 14 | | | 150-199, 275-299 |
| 031 | 24 | | PK | 80-0 | 28-41-21 | D04448J | | 15 | | | | | D04594J | 15 | | | 050-099 |
| 031 | 24 | | PK | 91-0 | 28-41-21 | D04448J | | 15 | | | | | D04594J | 15 | | | 150-199, 275-299 |
| 032 | 22 | | PQ | AR | 76-0 | 28-41-21 | D04904P | | 15 | | | | D04414J | 7 | | | 050-099 |
| 032 | 22 | | PQ | AR | 86-0 | 28-41-21 | D04904P | | 15 | | | | D04414J | 7 | | | 150-199, 275-299 |
| 032Z | | | | AR | 0-0 | 28-41-21 | D04904P | DED | | | | | D04414J | DED | | | ALL |
| 034 | 24 | | PK | 14-0 | 21-58-13 | D04904P | | 22 | | | | | D08004J | 5 | | | ALL |
| 039 | 24 | | PK | 14-0 | 21-58-13 | D04904P | | 34 | | | | | D08004J | 4 | | | ALL |
| 047 | 24 | | PK | 14-0 | 21-58-13 | D04904P | | 35 | | | | | D08004J | 6 | | | ALL |
| 061 | 12 | | PA | 11-0 | 21-58-14 | D04906P | | 6 | | | | | D06074J | 1 | | | ALL |
| 062 | 12 | | PA | 11-0 | 21-58-14 | D04906P | | 8 | | | | | D06074J | 2 | | | ALL |
| 063 | 12 | | PA | 11-0 | 21-58-14 | D04906P | | 10 | | | | | D06074J | 3 | | | ALL |
| 064 | 18 | | PA | 24-10 | 21-58-14 | D08112P | | 11 | DK | | | | D06074J | 4 | | | ALL |
| 065 | 24 | | PK | 29-10 | 21-58-14 | D04904P | | 30 | | | | | D08112P | 8 | | | ALL |
| 067 | 24 | | PK | 29-10 | 21-58-14 | D04904P | | 32 | | | | | D08112P | 10 | | | ALL |
| 072 | 24 | | PK | 14-0 | 21-58-12 | D04904P | | 42 | | | | | D08004J | 30 | | | ALL |
| 073 | 24 | | PK | 14-0 | 21-58-12 | D04904P | | 43 | | | | | D08004J | 33 | | | ALL |
| 081 | 24 | | PK | 28-0 | 21-51-11 | D06734J | | 45 | | | | | D06658P | 18 | | | ALL |
| 085 | 24 | | PK | 63-0 | 21-61-11 | D05686J | | 13 | | | | | D05048J | 20 | | | 050-099 |
| 085 | 24 | | PK | 73-0 | 21-61-11 | D05686J | | 13 | | | | | D05048J | 20 | | | 150-199, 275-299 |
| 086 | 24 | | PK | 63-0 | 21-61-11 | D05686J | | 14 | | | | | D05048J | 21 | | | 050-099 |
| 086 | 24 | | PK | 73-0 | 21-61-11 | D05686J | | 14 | | | | | D05048J | 21 | | | 150-199, 275-299 |
| 088 | 24 | | PK | 63-0 | 21-61-21 | D05686J | | 18 | | | | | D05048J | 25 | | | 050-099 |
| 088 | 24 | | PK | 73-0 | 21-61-21 | D05686J | | 18 | | | | | D05048J | 25 | | | 150-199, 275-299 |
| 089 | 24 | | PK | 63-0 | 21-61-21 | D05686J | | 19 | | | | | D05048J | 26 | | | 050-099 |
| 089 | 24 | | PK | 73-0 | 21-61-21 | D05686J | | 19 | | | | | D05048J | 26 | | | 150-199, 275-299 |
| 090 | 24 | | PK | 63-0 | 21-61-31 | D05686J | | 23 | | | | | D05048J | 30 | | | 050-099 |
| 090 | 24 | | PK | 73-0 | 21-61-31 | D05686J | | 23 | | | | | D05048J | 30 | | | 150-199, 275-299 |
| 091 | 24 | | PK | 63-0 | 21-61-31 | D05686J | | 24 | | | | | D05048J | 31 | | | 050-099 |
| 091 | 24 | | PK | 73-0 | 21-61-31 | D05686J | | 24 | | | | | D05048J | 31 | | | 150-199, 275-299 |
| 092 | 24 | | PK | 50-0 | 36-11-11 | D04904P | | 29 | | | | | D08042J | 19 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0940

Page 2

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | | | |
| 092 | 24 | | PK | 60-0 | 36-11-11 | D04904P | | | 29 | | | | D08042J | 19 | | | 150-199, 275-299 |
| 093 | 24 | | PK | 50-0 | 36-11-11 | D04904P | | | 33 | | | | D08042J | 20 | | | 050-099 |
| 093 | 24 | | PK | 60-0 | 36-11-11 | D04904P | | | 33 | | | | D08042J | 20 | | | 150-199, 275-299 |
| 094 | 24 | | PK | 50-0 | 36-11-11 | D04904P | | | 53 | | | | D08042J | 21 | | | 050-099 |
| 094 | 24 | | PK | 60-0 | 36-11-11 | D04904P | | | 53 | | | | D08042J | 21 | | | 150-199, 275-299 |
| 095 | 24 | | PK | 50-0 | 36-11-11 | D04904P | | | 54 | | | | D08042J | 22 | | | 050-099 |
| 095 | 24 | | PK | 60-0 | 36-11-11 | D04904P | | | 54 | | | | D08042J | 22 | | | 150-199, 275-299 |
| 104 | 24 | | PK | 14-0 | 21-58-12 | D08004J | | | 22 | | | | D04904P | 51 | | | ALL |
| 105 | 24 | | PK | 14-0 | 21-58-12 | D08004J | | | 25 | | | | D04904P | 49 | | | ALL |
| 108 | 20 | | PA | 78-0 | 27-13-11 | D04414J | | | 8 | | | | D04906P | 12 | | | 050-099 |
| 108 | 20 | | PA | 86-0 | 27-13-11 | D04414J | | | 8 | | | | D04906P | 12 | | | 150-199, 275-299 |
| 109 | 20 | | PA | 78-0 | 27-13-11 | D04414J | | | 9 | | | | D04906P | 13 | | | 050-099 |
| 109 | 20 | | PA | 86-0 | 27-13-11 | D04414J | | | 9 | | | | D04906P | 13 | | | 150-199, 275-299 |
| 110 | 22 | | PA | 78-0 | 27-13-11 | D04414J | | | 10 | | | | D04906P | 14 | | | 050-099 |
| 110 | 22 | | PA | 86-0 | 27-13-11 | D04414J | | | 10 | | | | D04906P | 14 | | | 150-199, 275-299 |
| 111 | 24 | | PK | 14-0 | 32-42-11 | D04906P | | | 9 | | | | D04908J | 4 | | | ALL |
| 123 | 16 | | PA | 78-0 | SPARE | D04906P | | | 1 | | | | D05562J | 4 | | | 050-099 |
| 123 | 16 | | PA | 86-0 | SPARE | D04906P | | | 1 | | | | D05562J | 4 | | | 150-199, 275-299 |
| 124 | 22 | | PA | 71-0 | SPARE | D04908J | | | 10 | | | | D04414J | 11 | | | 050-099 |
| 124 | 22 | | PA | 81-0 | SPARE | D04908J | | | 10 | | | | D04414J | 11 | | | 150-199, 275-299 |
| 125R | 22 | | PH | 50-0 | 26-18-11 | D04904P | | | 12 | | | | D08042J | 28 | | | 050-099 |
| 125R | 22 | | PH | 63-0 | 26-18-11 | D04904P | | | 12 | | | | D08042J | 28 | | | 150-199, 275-299 |
| 126 | 24 | | PK | 50-0 | 21-51-11 | D04904P | | | 58 | | | | D05988J | 3 | | | 050-099 |
| 126 | 24 | | PK | 63-0 | 21-51-11 | D04904P | | | 58 | | | | D05988J | 3 | | | 150-199, 275-299 |
| 128 | 24 | | PK | 12-0 | 21-58-11 | D04906P | | | 3 | | | | D06242P | A17 | \$D | | ALL |
| 129 | 24 | | PK | 34-7 | 21-58-11 | D08112P | | | 34 | | | | D06242P | A16 | \$D | | ALL |
| 130 | 24 | | PK | 34-7 | 21-58-14 | D08112P | | | 1 | | | | D06242P | A18 | \$D | | ALL |
| 132 | 24 | | PK | 34-7 | 21-58-15 | D08112P | | | 3 | | | | D06242P | B11 | \$D | | ALL |
| 133 | 24 | | PK | 34-7 | 21-26-11 | D08112P | | | 12 | | | | D06242P | B15 | \$D | | ALL |
| 134 | 24 | | PK | 34-7 | 21-26-11 | D08112P | | | 13 | | | | D06242P | B16 | \$D | | ALL |
| 135 | 24 | | PK | 12-0 | 21-44-21 | D04904P | | | 16 | | | | D06246P | A12 | \$D | | ALL |
| 136 | 22 | | PA | 12-0 | 73-21-14 | D04904P | | | 31 | | | | D06246P | A13 | \$D | | ALL |
| 137 | 24 | | PK | 23-0 | 21-51-11 | D06734J | | | 41 | | | | D06242P | B17 | \$D | | 050, 150-154, 275-276 |
| 137 | 24 | | PK | 23-0 | SPARE | D06734J | | | 41 | | | | D06242P | B17 | \$D | | 051-099, 155-199, 277-299 |
| 138 | 24 | | PK | 23-0 | 21-51-11 | D06734J | | | 44 | | | | D06242P | B18 | \$D | | ALL |
| 139 | 24 | | PK | 23-0 | 21-28-11 | D06734J | | | 43 | | | | D06242P | A13 | \$D | | 050-099, 155-199, 277-299 |
| 139 | 24 | | PK | 23-0 | 21-51-11 | D06734J | | | 43 | | | | D06242P | A13 | \$D | | 150-154, 275-276 |

WIRE LIST
D280T132

91-21-11
Section W0940
Page 3
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | |
| 140 | 24 | | PK | | 23-0 | 21-51-11 | D06734J | | | | D06242P | A12 | \$D | | ALL |
| 141 | 24 | | PK | | 36-0 | 21-51-11 | D04500J | | | | D06242P | A14 | \$D | | ALL |
| 142 | 24 | | PK | | 34-7 | 21-51-21 | D08112P | | | | D06242P | B12 | \$D | | ALL |
| 143 | 24 | | PK | | 34-7 | 21-51-21 | D08112P | | | | D06242P | B13 | \$D | | ALL |
| 144 | 24 | | PK | | 12-0 | 21-58-11 | D04906P | | | | D06246P | B14 | \$D | | ALL |
| 145 | 24 | | PK | | 34-8 | 36-11-51 | D08112P | | | | D06246P | A02 | \$D | | ALL |
| 146 | 24 | | PK | | 34-8 | 36-11-52 | D08112P | | | | D06246P | A03 | \$D | | ALL |
| 147 | 24 | | PK | | 34-8 | 36-22-11 | D08112P | | | | D06246P | A04 | \$D | | ALL |
| 148 | 24 | | PK | | 34-8 | 36-22-11 | D08112P | | | | D06246P | A05 | \$D | | ALL |
| 149 | 24 | | PK | | 50-0 | 36-21-11 | D05988J | | | | D04904P | 11 | | | 050-099 |
| 149 | 24 | | PK | | 63-0 | 36-21-11 | D05988J | | | | D04904P | 11 | | | 150-199, 275-299 |
| 150 | 24 | | PK | | 34-8 | 36-11-62 | D08112P | | | | D06246P | A08 | \$D | | ALL |
| 151 | 24 | | PK | | 34-8 | 36-11-61 | D08112P | | | 4 | D06246P | A09 | \$D | | ALL |
| 152 | 24 | | PK | | 1-0 | SPARE | D06246P | | CAP | Y | D06246P | A10 | \$D | | 050-099 |
| 152 | 24 | | PK | | 34-8 | SPARE | D08112P | | | 26 | D06246P | A10 | \$D | | 275-299 |
| 153 | 24 | | PK | | 1-0 | SPARE | D06246P | | CAP | Y | D06246P | A11 | \$D | | 050-099 |
| 153 | 24 | | PK | | 34-8 | SPARE | D08112P | | | 27 | D06246P | A11 | \$D | | 275-299 |
| 157 | 24 | | PK | | 34-8 | 73-21-18 | D08112P | | | 22 | D06246P | A14 | \$D | | ALL |
| 158 | 24 | | PK | | 14-0 | 32-42-11 | D04906P | | | 15 | D04908J | 11 | | | ALL |
| 159 | 24 | | PK | | 14-0 | 32-42-11 | D04906P | | | 16 | D04908J | 12 | | | ALL |
| 160 | 24 | | PK | | 14-0 | 32-42-11 | D04906P | | | 17 | D04908J | 13 | | | ALL |
| 161 | 24 | | PK | | 14-0 | 32-42-11 | D04906P | | | 18 | D04908J | 14 | | | ALL |
| 162 | 24 | | PK | | 14-0 | 32-42-11 | D04906P | | | 19 | D04908J | 15 | | | ALL |
| 163 | 24 | | PK | | 14-0 | 32-42-11 | D04906P | | | 20 | D04908J | 16 | | | ALL |
| 164 | 24 | | PK | | 14-0 | 32-42-11 | D04906P | | | 7 | D04908J | 17 | | | ALL |
| 165 | 24 | | PK | | 12-0 | 21-58-11 | D04906P | | | 21 | D06246P | A17 | \$D | | ALL |
| 167 | 24 | | PK | | 29-10 | 21-58-14 | D04904P | | | 4 | D08112P | 33 | | | ALL |
| 168 | 24 | | PK | | 62-0 | 21-61-41 | D05686J | | | 31 | D05988J | 16 | | | 050-099 |
| 168 | 24 | | PK | | 73-0 | 21-61-41 | D05686J | | | 31 | D05988J | 16 | | | 150-199, 275-299 |
| 169 | 24 | | PK | | 62-0 | 21-61-41 | D05686J | | | 34 | D05988J | 17 | | | 050-099 |
| 169 | 24 | | PK | | 73-0 | 21-61-41 | D05686J | | | 34 | D05988J | 17 | | | 150-199, 275-299 |
| 172 | 24 | | PK | | 62-0 | 21-61-11 | D05686J | | | 48 | D05988J | 24 | | | 050-099 |
| 172 | 24 | | PK | | 73-0 | 21-61-11 | D05686J | | | 48 | D05988J | 24 | | | 150-199, 275-299 |
| 173 | 24 | | PK | | 62-0 | 21-61-11 | D05686J | | | 49 | D05988J | 25 | | | 050-099 |
| 173 | 24 | | PK | | 73-0 | 21-61-11 | D05686J | | | 49 | D05988J | 25 | | | 150-199, 275-299 |
| 174 | 24 | | PK | | 62-0 | 21-61-21 | D05686J | | | 50 | D05988J | 26 | | | 050-099 |
| 174 | 24 | | PK | | 73-0 | 21-61-21 | D05686J | | | 50 | D05988J | 26 | | | 150-199, 275-299 |
| 175 | 24 | | PK | | 62-0 | 21-61-21 | D05686J | | | 51 | D05988J | 27 | | | 050-099 |
| 175 | 24 | | PK | | 73-0 | 21-61-21 | D05686J | | | 51 | D05988J | 27 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0940

Page 4

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | | | |
| 176 | 24 | | PK | 62-0 | 21-61-31 | D05686J | | 52 | | | | | D05988J | 28 | | | 050-099 |
| 176 | 24 | | PK | 73-0 | 21-61-31 | D05686J | | 52 | | | | | D05988J | 28 | | | 150-199, 275-299 |
| 177 | 24 | | PK | 62-0 | 21-61-31 | D05686J | | 53 | | | | | D05988J | 29 | | | 050-099 |
| 177 | 24 | | PK | 73-0 | 21-61-31 | D05686J | | 53 | | | | | D05988J | 29 | | | 150-199, 275-299 |
| 179 | 24 | | PK | 62-0 | 21-61-41 | D05686J | | 54 | | | | | D05988J | 30 | | | 050-099 |
| 179 | 24 | | PK | 73-0 | 21-61-41 | D05686J | | 54 | | | | | D05988J | 30 | | | 150-199, 275-299 |
| 180 | 24 | | PK | 62-0 | 21-61-41 | D05686J | | 55 | | | | | D05988J | 31 | | | 050-099 |
| 180 | 24 | | PK | 73-0 | 21-61-41 | D05686J | | 55 | | | | | D05988J | 31 | | | 150-199, 275-299 |
| 185 | 24 | | PK | 29-10 | 36-11-61 | D04904P | | 40 | | | | | D08112P | 40 | | | ALL |
| 187 | 24 | | PK | 29-10 | 36-11-61 | D04904P | | 39 | | | | | D08112P | 39 | | | ALL |
| 188 | 24 | | PK | 29-10 | 36-11-61 | D04904P | | 38 | | | | | D08112P | 38 | | | ALL |
| 189 | 22 | | PA | 29-10 | 36-11-61 | D04904P | | 37 | | | | | D08112P | 37 | | | ALL |
| 190 | 22 | | PA | 29-10 | 36-11-61 | D04904P | | 36 | | | | | D08112P | 36 | | | ALL |
| 191 | 24 | | PK | 34-8 | 36-11-61 | D06246P | | B02 | \$D | | | | D08112P | 23 | | | ALL |
| 192 | 24 | | PK | 34-7 | 36-11-62 | D06242P | | B14 | \$D | | | | D08112P | 24 | | | ALL |
| 202B | 22 | | PB | IB | 55-0 | 21-52-31 | D06242P | A08 | \$D | | | | D05048J | 5 | | | 050-099 |
| 202B | 22 | | PB | IB | 65-0 | 21-52-31 | D06242P | A08 | \$D | | | | D05048J | 5 | | | 150-199 |
| 202B | 22 | | PB | F | 65-0 | 21-52-31 | D06242P | A08 | \$D | | | | D05048J | 5 | | | 275-299 |
| 202R | 22 | | PB | IB | 0-0 | 21-52-31 | D06242P | A09 | \$D | | | | D05048J | 6 | | | 050-099, 150-199 |
| 202R | 22 | | PB | F | 0-0 | 21-52-31 | D06242P | A09 | \$D | | | | D05048J | 6 | | | 275-299 |
| 204B | 22 | | PB | L | 63-0 | 21-51-12 | D04500J | 20 | | | | | D05048J | 18 | | | 050-099 |
| 204B | 22 | | PB | L | 73-0 | 21-51-12 | D04500J | 20 | | | | | D05048J | 18 | | | 150-199, 275-299 |
| 204R | 22 | | PB | L | 0-0 | 21-51-12 | D04500J | 19 | | | | | D05048J | 19 | | | ALL |
| 205B | 22 | | PB | M | 63-0 | 21-51-12 | D04500J | 22 | | | | | D05048J | 16 | | | 050-099 |
| 205B | 22 | | PB | M | 73-0 | 21-51-12 | D04500J | 22 | | | | | D05048J | 16 | | | 150-199, 275-299 |
| 205R | 22 | | PB | M | 0-0 | 21-51-12 | D04500J | 21 | | | | | D05048J | 17 | | | ALL |
| 206B | 24 | | PL | N | 32-0 | 21-51-12 | D04500J | 13 | | | | | D04904P | 13 | | | ALL |
| 206R | 24 | | PL | N | 0-0 | 21-51-12 | D04500J | 14 | | | | | D04904P | 14 | | | ALL |
| 207B | 22 | | PB | O | 24-0 | 21-51-12 | D04500J | 15 | | | | | D08004J | 1 | | | ALL |
| 207R | 22 | | PB | O | 0-0 | 21-51-12 | D04500J | 16 | | | | | D08004J | 2 | | | ALL |
| 209B | 24 | | PL | AF | 80-0 | 28-41-21 | D04448J | 16 | | | | | D04414J | 3 | | | 050-099 |
| 209B | 24 | | PL | AF | 89-0 | 28-41-21 | D04448J | 16 | | | | | D04414J | 3 | | | 150-199, 275-299 |
| 209R | 24 | | PL | AF | 0-0 | 28-41-21 | D04448J | 17 | | | | | D04414J | 4 | | | ALL |
| 210B | 24 | | PL | AE | 80-0 | 28-41-21 | D04448J | 18 | | | | | D04414J | 5 | | | 050-099 |
| 210B | 24 | | PL | AE | 89-0 | 28-41-21 | D04448J | 18 | | | | | D04414J | 5 | | | 150-199, 275-299 |
| 210R | 24 | | PL | AE | 0-0 | 28-41-21 | D04448J | 19 | | | | | D04414J | 6 | | | ALL |
| 212B | 24 | | PL | S | 50-0 | 36-21-11 | D04904P | 61 | | | | | D05048J | 51 | | | 050-099 |
| 212B | 24 | | PL | S | 60-0 | 36-21-11 | D04904P | 61 | | | | | D05048J | 51 | | | 150-199, 275-299 |
| 212R | 24 | | PL | S | 0-0 | 36-21-11 | D04904P | 60 | | | | | D05048J | 50 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0940

Page 5

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | | |
| 213B | 24 | PL | Z | | 63-0 | 21-52-41 | D04500J | | | | | | | | 8 | 050-099 |
| 213B | 24 | PL | Z | | 73-0 | 21-52-41 | D04500J | | | | | | | | 8 | 150-199, 275-299 |
| 213R | 24 | PL | Z | | 0-0 | 21-52-41 | D04500J | | | | | | | | 7 | ALL |
| 214B | 24 | PL | Y | | 63-0 | 21-52-41 | D05686J | | | | | | | | 44 | 050-099 |
| 214B | 24 | PL | Y | | 73-0 | 21-52-41 | D05686J | | | | | | | | 44 | 150-199, 275-299 |
| 214R | 24 | PL | Y | | 0-0 | 21-52-41 | D05686J | | | | | | | | 9 | ALL |
| 216B | 24 | PW | AH | | 14-0 | 32-42-11 | D04906P | | | | | | | | 2 | ALL |
| 216R | 24 | PW | AH | | 0-0 | 32-42-11 | D04906P | | | | | | | | 1 | ALL |
| 216Z | | | | AH | 0-0 | 32-42-11 | D04906P | | | | | | | | 3 | ALL |
| 217B | 22 | PB | IQ | | 54-0 | 21-52-31 | D06246P | A18 | \$D | | | | | | 13 | 050-099 |
| 217B | 22 | PB | IQ | | 64-0 | 21-52-31 | D06246P | A18 | \$D | | | | | | 13 | 150-199 |
| 217B | 22 | PB | IQ | | 65-0 | 21-52-31 | D06246P | A18 | \$D | | | | | | 13 | 275-299 |
| 217R | 22 | PB | IQ | | 0-0 | 21-52-31 | D06246P | A19 | \$D | | | | | | 14 | ALL |
| 218B | 22 | PB | IR | | 54-0 | 21-52-31 | D06246P | B05 | \$D | | | | | | 9 | 050-099 |
| 218B | 22 | PB | IR | | 64-0 | 21-52-31 | D06246P | B05 | \$D | | | | | | 9 | 150-199 |
| 218B | 22 | PB | IR | | 65-0 | 21-52-31 | D06246P | B05 | \$D | | | | | | 9 | 275-299 |
| 218R | 22 | PB | IR | | 0-0 | 21-52-31 | D06246P | B06 | \$D | | | | | | 10 | ALL |
| 219B | 22 | PB | IS | | 54-0 | 21-52-31 | D06246P | B09 | \$D | | | | | | 11 | 050-099 |
| 219B | 22 | PB | IS | | 64-0 | 21-52-31 | D06246P | B09 | \$D | | | | | | 11 | 150-199 |
| 219B | 22 | PB | IS | | 65-0 | 21-52-31 | D06246P | B09 | \$D | | | | | | 11 | 275-299 |
| 219R | 22 | PB | IS | | 0-0 | 21-52-31 | D06246P | B10 | \$D | | | | | | 12 | ALL |
| 220B | 22 | PB | AM | | 62-0 | 21-51-12 | D05686J | | | | | | | | 2 | 050-099 |
| 220B | 22 | PB | AM | | 73-0 | 21-51-12 | D05686J | | | | | | | | 2 | 150-199, 275-299 |
| 220R | 22 | PB | AM | | 0-0 | 21-51-12 | D05686J | | | | | | | | 1 | ALL |
| 221B | 24 | PL | AP | | 36-0 | 21-52-41 | D04500J | | | | | | | | 44 | ALL |
| 221R | 24 | PL | AP | | 0-0 | 21-52-41 | D04500J | | | | | | | | A11 | \$D |
| 224B | 22 | PB | IX | | 54-0 | 21-52-31 | D06246P | B15 | \$D | | | | | | 7 | 050-099 |
| 224B | 22 | PB | IX | | 64-0 | 21-52-31 | D06246P | B15 | \$D | | | | | | 7 | 150-199 |
| 224B | 22 | PB | IX | | 65-0 | 21-52-31 | D06246P | B15 | \$D | | | | | | 7 | 275-299 |
| 224R | 22 | PB | IX | | 0-0 | 21-52-31 | D06246P | B16 | \$D | | | | | | 4 | ALL |
| 225B | 22 | PB | IY | | 54-0 | 21-52-31 | D06246P | B07 | \$D | | | | | | 54 | 050-099 |
| 225B | 22 | PB | IY | | 65-0 | 21-52-31 | D06246P | B07 | \$D | | | | | | 54 | 150-199, 275-299 |
| 225R | 22 | PB | IY | | 0-0 | 21-52-31 | D06246P | B08 | \$D | | | | | | 55 | ALL |
| 226B | 24 | PL | AO | | 12-0 | 36-21-11 | D04904P | | | | | | | | 7 | ALL |
| 226R | 24 | PL | AO | | 0-0 | 36-21-11 | D04904P | | | | | | | | 6 | ALL |
| 227B | 24 | PW | JB | | 29-10 | 77-12-12 | D08112P | | | | | | | | 9 | ALL |
| 227R | 24 | PW | JB | | 0-0 | 77-12-12 | D08112P | | | | | | | | 8 | ALL |
| 227Z | | | | JB | 0-0 | 77-12-12 | D08112P | | | | | | | | 43 | ALL |
| 228B | 24 | PL | JC | | 17-0 | 21-61-51 | D04904P | | | | | | | | 3 | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0940

Page 6

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | |
| 228B | 24 | PL | JC | | 18-0 | 21-61-51 | D04904P | | | 3 | D06734J | | | 13 | 275-299 |
| 228R | 24 | PL | JC | | 0-0 | 21-61-51 | D04904P | | | 5 | D06734J | | | 14 | ALL |
| 229B | 24 | PL | JD | | 17-0 | 21-61-51 | D06734J | | | 3 | D04906P | | | 25 | 050-099, 150-199 |
| 229B | 24 | PL | JD | | 18-0 | 21-61-51 | D06734J | | | 3 | D04906P | | | 25 | 275-299 |
| 229R | 24 | PL | JD | | 0-0 | 21-61-51 | D06734J | | | 4 | D04906P | | | 26 | ALL |
| 230B | 24 | PL | JE | | 28-0 | 21-61-51 | D06734J | | | 5 | D05686J | | | 36 | ALL |
| 230R | 24 | PL | JE | | 0-0 | 21-61-51 | D06734J | | | 6 | D05686J | | | 38 | ALL |
| 231B | 24 | PL | JF | | 28-0 | 21-61-51 | D06734J | | | 7 | D05686J | | | 46 | ALL |
| 231R | 24 | PL | JF | | 0-0 | 21-61-51 | D06734J | | | 8 | D05686J | | | 47 | ALL |
| 232B | 24 | PL | JG | | 28-0 | 21-61-51 | D06734J | | | 9 | D05686J | | | 42 | ALL |
| 232R | 24 | PL | JG | | 0-0 | 21-61-51 | D06734J | | | 10 | D05686J | | | 43 | ALL |
| 233B | 24 | PL | JH | | 28-0 | 21-61-51 | D06734J | | | 11 | D04500J | | | 38 | ALL |
| 233R | 24 | PL | JH | | 0-0 | 21-61-51 | D06734J | | | 12 | D04500J | | | 39 | ALL |
| 234B | 24 | PL | JI | | 31-0 | 21-61-51 | D05686J | | | 44 | D04906P | | | 28 | ALL |
| 234R | 24 | PL | JI | | 0-0 | 21-61-51 | D05686J | | | 45 | D04906P | | | 27 | ALL |
| 235B | 24 | PL | JJ | | 24-0 | 21-28-11 | D06734J | | | 40 | D06246P | B04 | \$D | | 050-099, 275-299 |
| 235B | 24 | PL | JJ | | 24-0 | 21-28-11 | D06734J | | | 40 | D06246P | B04 | | | 150-199 |
| 235R | 24 | PL | JJ | | 0-0 | 21-28-11 | D06734J | | | 39 | D06246P | B03 | \$D | | 050-099, 275-299 |
| 235R | 24 | PL | JJ | | 0-0 | 21-28-11 | D06734J | | | 39 | D06246P | B03 | | | 150-199 |
| 236B | 24 | PL | JK | | 27-0 | 21-61-81 | D08680P | | | 5 | D06754J | | | 13 | ALL |
| 236R | 24 | PL | JK | | 0-0 | 21-61-81 | D08680P | | | 4 | D06754J | | | 12 | ALL |
| 237B | 24 | PL | JL | | 48-0 | 21-61-81 | D13592 | | | 1 | D06754J | | | 1 | 050-099 |
| 237B | 24 | PL | JL | | 58-0 | 21-61-81 | D13592 | | | 1 | D06754J | | | 1 | 150-199, 275-299 |
| 237R | 24 | PL | JL | | 0-0 | 21-61-81 | D13592 | | | 2 | D06754J | | | 2 | ALL |
| 238B | 24 | PL | JM | | 7-0 | 21-61-81 | D06754J | | | 4 | D08004J | | | 17 | 050-099 |
| 238B | 24 | PL | JM | | 8-0 | 21-61-81 | D06754J | | | 4 | D08004J | | | 17 | 150-199, 275-299 |
| 238R | 24 | PL | JM | | 0-0 | 21-61-81 | D06754J | | | 3 | D08004J | | | 16 | ALL |
| 239B | 24 | PL | JN | | 18-0 | 21-43-12 | D08004J | | | 18 | D06242P | A15 | \$D | | 050-099 |
| 239B | 24 | PL | JN | | 19-0 | 21-43-12 | D08004J | | | 18 | D06242P | A15 | | | 150-199 |
| 239B | 24 | PL | JN | | 19-0 | 21-43-12 | D08004J | | | 18 | D06242P | A15 | \$D | | 275-299 |
| 239R | 24 | PL | JN | | 0-0 | 21-43-12 | D08004J | | | 19 | D06242P | A19 | \$D | | 050-099, 275-299 |
| 239R | 24 | PL | JN | | 0-0 | 21-43-12 | D08004J | | | 19 | D06242P | A19 | | | 150-199 |
| 240B | 22 | PB | JO | | 6-0 | 21-61-81 | D05686J | | | 6 | D08680P | | | 21 | 050-099, 151-199, 275-299 |
| 240R | 22 | PB | JO | | 0-0 | 21-61-81 | D05686J | | | 7 | D08680P | | | 20 | 050-099, 151-199, 275-299 |
| 241B | 22 | PB | JP | | 26-0 | 21-61-81 | D06754J | | | 24 | D08680P | | | 23 | 050-099 |
| 241B | 22 | PB | JP | | 28-0 | 21-61-81 | D06754J | | | 24 | D08680P | | | 23 | 151-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W0940
Page 7
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | | | |
| 241R | 22 | PB | JP | 0-0 | 21-61-81 | D06754J | | 23 | | | | | D08680P | 22 | | | 050-099, 151-199, 275-299 |
| 301B | 24 | PM | A | 63-0 | 21-53-11 | D04500J | | 1 | | | | | D08042J | 1 | | | 050-099 |
| 301B | 24 | PM | A | 73-0 | 21-53-11 | D04500J | | 1 | | | | | D08042J | 1 | | | 150-199, 275-299 |
| 301R | 24 | PM | A | 0-0 | 21-53-11 | D04500J | | 2 | | | | | D08042J | 2 | | | ALL |
| 301Y | 24 | PM | A | 0-0 | 21-53-11 | D04500J | | 3 | | | | | D08042J | 3 | | | ALL |
| 302B | 24 | PM | B | 63-0 | 21-53-11 | D04500J | | 4 | | | | | D08042J | 4 | | | 050-099 |
| 302B | 24 | PM | B | 73-0 | 21-53-11 | D04500J | | 4 | | | | | D08042J | 4 | | | 150-199, 275-299 |
| 302R | 24 | PM | B | 0-0 | 21-53-11 | D04500J | | 5 | | | | | D08042J | 5 | | | ALL |
| 302Y | 24 | PM | B | 0-0 | 21-53-11 | D04500J | | 6 | | | | | D08042J | 6 | | | ALL |
| 303B | 24 | PM | C | 63-0 | 21-53-11 | D04500J | | 7 | | | | | D08042J | 7 | | | 050-099 |
| 303B | 24 | PM | C | 73-0 | 21-53-11 | D04500J | | 7 | | | | | D08042J | 7 | | | 150-199, 275-299 |
| 303R | 24 | PM | C | 0-0 | 21-53-11 | D04500J | | 8 | | | | | D08042J | 8 | | | ALL |
| 303Y | 24 | PM | C | 0-0 | 21-53-11 | D04500J | | 9 | | | | | D08042J | 9 | | | ALL |
| 304B | 24 | PM | D | 54-0 | 21-52-11 | D06242P | | A05 | \$D | | | | D08042J | 10 | | | 050-099 |
| 304B | 24 | PM | D | 64-0 | 21-52-11 | D06242P | | A05 | \$D | | | | D08042J | 10 | | | 150-199, 275-299 |
| 304R | 24 | PM | D | 0-0 | 21-52-11 | D06242P | | A06 | \$D | | | | D08042J | 11 | | | ALL |
| 304Y | 24 | PM | D | 0-0 | 21-52-11 | D06242P | | A07 | \$D | | | | D08042J | 12 | | | ALL |
| 305B | 24 | PM | E | 54-0 | 21-52-11 | D06242P | | A02 | \$D | | | | D05048J | 2 | | | 050-099 |
| 305B | 24 | PM | E | 64-0 | 21-52-11 | D06242P | | A02 | \$D | | | | D05048J | 2 | | | 150-199, 275-299 |
| 305R | 24 | PM | E | 0-0 | 21-52-11 | D06242P | | A03 | \$D | | | | D05048J | 3 | | | ALL |
| 305Y | 24 | PM | E | 0-0 | 21-52-11 | D06242P | | A04 | \$D | | | | D05048J | 4 | | | ALL |
| 306B | 22 | PC | H | 63-0 | 21-51-12 | D04500J | | 28 | | | | | D08042J | 16 | | | 050-099 |
| 306B | 22 | PC | H | 73-0 | 21-51-12 | D04500J | | 28 | | | | | D08042J | 16 | | | 150-199, 275-299 |
| 306R | 22 | PC | H | 0-0 | 21-51-12 | D04500J | | 27 | | | | | D08042J | 17 | | | ALL |
| 306Y | 22 | PC | H | 0-0 | 21-51-12 | D04500J | | 26 | | | | | D08042J | 18 | | | ALL |
| 307B | 22 | PC | I | 63-0 | 21-51-12 | D04500J | | 31 | | | | | D08042J | 13 | | | 050-099 |
| 307B | 22 | PC | I | 73-0 | 21-51-12 | D04500J | | 31 | | | | | D08042J | 13 | | | 150-199, 275-299 |
| 307R | 22 | PC | I | 0-0 | 21-51-12 | D04500J | | 30 | | | | | D08042J | 14 | | | ALL |
| 307Y | 22 | PC | I | 0-0 | 21-51-12 | D04500J | | 29 | | | | | D08042J | 15 | | | ALL |
| 308B | 22 | PC | J | 63-0 | 21-51-12 | D04500J | | 25 | | | | | D05048J | 13 | | | 050-099 |
| 308B | 22 | PC | J | 73-0 | 21-51-12 | D04500J | | 25 | | | | | D05048J | 13 | | | 150-199, 275-299 |
| 308R | 22 | PC | J | 0-0 | 21-51-12 | D04500J | | 24 | | | | | D05048J | 14 | | | ALL |
| 308Y | 22 | PC | J | 0-0 | 21-51-12 | D04500J | | 23 | | | | | D05048J | 15 | | | ALL |
| 309B | 24 | PM | K | 63-0 | 21-51-12 | D04500J | | 10 | | | | | D05048J | 10 | | | 050-099 |
| 309B | 24 | PM | K | 73-0 | 21-51-12 | D04500J | | 10 | | | | | D05048J | 10 | | | 150-199, 275-299 |
| 309R | 24 | PM | K | 0-0 | 21-51-12 | D04500J | | 11 | | | | | D05048J | 11 | | | ALL |
| 309Y | 24 | PM | K | 0-0 | 21-51-12 | D04500J | | 12 | | | | | D05048J | 12 | | | ALL |
| 310B | 24 | PM | AA | 63-0 | 21-61-11 | D05686J | | 10 | | | | | D05048J | 22 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0940

Page 8

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | | |
| 310B | 24 | PM | AA | 73-0 | 21-61-11 | D05686J | | 10 | | | | D05048J | 22 | | | 150-199, 275-299 |
| 310R | 24 | PM | AA | 0-0 | 21-61-11 | D05686J | | 11 | | | | D05048J | 23 | | | ALL |
| 310Y | 24 | PM | AA | 0-0 | 21-61-11 | D05686J | | 12 | | | | D05048J | 24 | | | ALL |
| 311B | 24 | PM | AB | 63-0 | 21-61-21 | D05686J | | 15 | | | | D05048J | 27 | | | 050-099 |
| 311B | 24 | PM | AB | 73-0 | 21-61-21 | D05686J | | 15 | | | | D05048J | 27 | | | 150-199, 275-299 |
| 311R | 24 | PM | AB | 0-0 | 21-61-21 | D05686J | | 16 | | | | D05048J | 28 | | | ALL |
| 311Y | 24 | PM | AB | 0-0 | 21-61-21 | D05686J | | 17 | | | | D05048J | 29 | | | ALL |
| 312B | 24 | PM | AC | 63-0 | 21-61-31 | D05686J | | 20 | | | | D05048J | 32 | | | 050-099 |
| 312B | 24 | PM | AC | 73-0 | 21-61-31 | D05686J | | 20 | | | | D05048J | 32 | | | 150-199, 275-299 |
| 312R | 24 | PM | AC | 0-0 | 21-61-31 | D05686J | | 21 | | | | D05048J | 33 | | | ALL |
| 312Y | 24 | PM | AC | 0-0 | 21-61-31 | D05686J | | 22 | | | | D05048J | 34 | | | ALL |
| 313B | 24 | PM | T | 54-0 | 21-64-11 | D06242P | | | B02 | \$D | | D05048J | 35 | | | 050-099 |
| 313B | 24 | PM | T | 64-0 | 21-64-11 | D06242P | | | B02 | \$D | | D05048J | 35 | | | 150-199, 275-299 |
| 313R | 24 | PM | T | 0-0 | 21-64-11 | D06242P | | | B03 | \$D | | D05048J | 36 | | | ALL |
| 313Y | 24 | PM | T | 0-0 | 21-64-11 | D06242P | | | B04 | \$D | | D05048J | 37 | | | ALL |
| 314B | 24 | PM | U | 54-0 | 21-64-11 | D06242P | | | B05 | \$D | | D05048J | 38 | | | 050-099 |
| 314B | 24 | PM | U | 64-0 | 21-64-11 | D06242P | | | B05 | \$D | | D05048J | 38 | | | 150-199, 275-299 |
| 314R | 24 | PM | U | 0-0 | 21-64-11 | D06242P | | | B06 | \$D | | D05048J | 39 | | | ALL |
| 314Y | 24 | PM | U | 0-0 | 21-64-11 | D06242P | | | B07 | \$D | | D05048J | 40 | | | ALL |
| 315B | 24 | PM | V | 54-0 | 21-64-11 | D06242P | | | B08 | \$D | | D05048J | 41 | | | 050-099 |
| 315B | 24 | PM | V | 64-0 | 21-64-11 | D06242P | | | B08 | \$D | | D05048J | 41 | | | 150-199, 275-299 |
| 315R | 24 | PM | V | 0-0 | 21-64-11 | D06242P | | | B09 | \$D | | D05048J | 42 | | | ALL |
| 315Y | 24 | PM | V | 0-0 | 21-64-11 | D06242P | | | B10 | \$D | | D05048J | 43 | | | ALL |
| 319B | 24 | PM | MS | 49-0 | 21-61-81 | D06754J | | 6 | | | | D05988J | 47 | | | 050-099 |
| 319B | 24 | PM | MS | 61-0 | 21-61-81 | D06754J | | 6 | | | | D05988J | 47 | | | 150-199, 275-299 |
| 319R | 24 | PM | MS | 0-0 | 21-61-81 | D06754J | | 5 | | | | D05988J | 46 | | | ALL |
| 319Y | 24 | PM | MS | 0-0 | 21-61-81 | D06754J | | 7 | | | | D05988J | 48 | | | ALL |
| 320B | 24 | PM | MT | 50-0 | 21-64-11 | SP03870 | | | | S | | D05988J | 55 | | | 050-099 |
| 320B | 24 | PM | MT | 60-0 | 21-64-11 | SP03870 | | | | S | | D05988J | 55 | | | 150-199 |
| 320B | 24 | PM | MT | 61-0 | 21-64-11 | SP03870 | | | | S | | D05988J | 55 | | | 275-299 |
| 320R | 24 | PM | MT | 0-0 | 21-64-11 | SP03872 | | | | S | | D05988J | 53 | | | ALL |
| 320Y | 24 | PM | MT | 0-0 | 21-64-11 | SP03874 | | | | S | | D05988J | 54 | | | ALL |
| 321B | 22 | PC | AL | 73-0 | SPARE | D04500J | | 52 | | | | D08042J | 23 | | | ALL |
| 321R | 22 | PC | AL | 0-0 | SPARE | D04500J | | 53 | | | | D08042J | 24 | | | ALL |
| 321Y | 22 | PC | AL | 0-0 | SPARE | D04500J | | 54 | | | | D08042J | 25 | | | ALL |
| 322B | 22 | PC | MV | 54-0 | 21-52-11 | D06246P | | | B11 | \$D | | D08042J | 29 | | | 050-099 |
| 322B | 22 | PC | MV | 65-0 | 21-52-11 | D06246P | | | B11 | | | D08042J | 29 | | | 150-199 |
| 322B | 22 | PC | MV | 65-0 | 21-52-11 | D06246P | | | B11 | \$D | | D08042J | 29 | | | 275-299 |
| 322R | 22 | PC | MV | 0-0 | 21-52-11 | D06246P | | | B12 | \$D | | D08042J | 30 | | | 050-099, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0940

Page 9

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | | |
| 322R | 22 | PC | MV | | 0-0 | 21-52-11 | D06246P | | B12 | | | | D08042J | 30 | | 150-199 |
| 322Y | 22 | PC | MV | | 0-0 | 21-52-11 | D06246P | | B13 | \$D | | | D08042J | 31 | | 050-099, 275-299 |
| 322Y | 22 | PC | MV | | 0-0 | 21-52-11 | D06246P | | B13 | | | | D08042J | 31 | | 150-199 |
| 323B | 24 | PM | AT | | 62-0 | 21-61-41 | D05686J | | 41 | | | | D05988J | 20 | | 050-099 |
| 323B | 24 | PM | AT | | 73-0 | 21-61-41 | D05686J | | 41 | | | | D05988J | 20 | | 150-199, 275-299 |
| 323R | 24 | PM | AT | | 0-0 | 21-61-41 | D05686J | | 40 | | | | D05988J | 19 | | ALL |
| 323Y | 24 | PM | AT | | 0-0 | 21-61-41 | D05686J | | 39 | | | | D05988J | 18 | | ALL |
| 324B | 24 | PM | AU | | 54-0 | 21-64-11 | D06246P | | B17 | \$D | | | D05988J | 21 | | 050-099 |
| 324B | 24 | PM | AU | | 64-0 | 21-64-11 | D06246P | | B17 | \$D | | | D05988J | 21 | | 150-199, 275-299 |
| 324R | 24 | PM | AU | | 0-0 | 21-64-11 | D06246P | | B19 | \$D | | | D05988J | 23 | | ALL |
| 324Y | 24 | PM | AU | | 0-0 | 21-64-11 | D06246P | | B18 | \$D | | | D05988J | 22 | | ALL |
| 325B | 24 | PM | MY | | 50-0 | 21-61-61 | D06734J | | 18 | | | | D05988J | 38 | | 050-099 |
| 325B | 24 | PM | MY | | 59-0 | 21-61-61 | D06734J | | 18 | | | | D05988J | 38 | | 150-199, 275-299 |
| 325R | 24 | PM | MY | | 0-0 | 21-61-61 | D06734J | | 17 | | | | D05988J | 37 | | ALL |
| 325Y | 24 | PM | MY | | 0-0 | 21-61-61 | D06734J | | 16 | | | | D05988J | 36 | | ALL |
| 326B | 24 | PM | NA | | 50-0 | 21-61-71 | D06734J | | 20 | | | | D05988J | 40 | | 050-099 |
| 326B | 24 | PM | NA | | 59-0 | 21-61-71 | D06734J | | 20 | | | | D05988J | 40 | | 150-199, 275-299 |
| 326R | 24 | PM | NA | | 0-0 | 21-61-71 | D06734J | | 19 | | | | D05988J | 39 | | ALL |
| 326Y | 24 | PM | NA | | 0-0 | 21-61-71 | D06734J | | 21 | | | | D05988J | 41 | | ALL |
| 327B | 24 | PM | NB | | 50-0 | 21-64-11 | SP03876 | | | S | | | D05048J | 49 | | 050-099 |
| 327B | 24 | PM | NB | | 60-0 | 21-64-11 | SP03876 | | | S | | | D05048J | 49 | | 150-199 |
| 327B | 24 | PM | NB | | 61-0 | 21-64-11 | SP03876 | | | S | | | D05048J | 49 | | 275-299 |
| 327R | 24 | PM | NB | | 0-0 | 21-64-11 | SP03880 | | | S | | | D05048J | 53 | | ALL |
| 327Y | 24 | PM | NB | | 0-0 | 21-64-11 | SP03878 | | | S | | | D05048J | 52 | | ALL |
| 401B | 24 | PN | X | | 63-0 | 21-52-41 | D05686J | | 30 | | | | D05048J | 45 | | 050-099 |
| 401B | 24 | PN | X | | 73-0 | 21-52-41 | D05686J | | 30 | | | | D05048J | 45 | | 150-199, 275-299 |
| 401G | 24 | PN | X | | 0-0 | 21-52-41 | D05686J | | 27 | | | | D05048J | 46 | | ALL |
| 401R | 24 | PN | X | | 0-0 | 21-52-41 | D05686J | | 28 | | | | D05048J | 47 | | ALL |
| 401Y | 24 | PN | X | | 0-0 | 21-52-41 | D05686J | | 29 | | | | D05048J | 48 | | ALL |
| 501 | 24 | PK | | | 29-10 | 21-58-11 | D04904P | | 41 | | | | D08112P | 18 | | ALL |
| 502 | 24 | PK | | | 17-0 | SPARE | D06734J | | 1 | | | | D04906P | 23 | | 050-099, 150-199 |
| 502 | 24 | PK | | | 18-0 | SPARE | D06734J | | 1 | | | | D04906P | 23 | | 275-299 |
| 503 | 24 | PK | | | 17-0 | 21-61-51 | D06734J | | 2 | | | | D04906P | 24 | | 050-099, 150-199 |
| 503 | 24 | PK | | | 18-0 | 21-61-51 | D06734J | | 2 | | | | D04906P | 24 | | 275-299 |
| 504 | 24 | PK | | | 50-0 | 21-61-61 | D04904P | | 17 | | | | D05988J | 32 | | 050-099 |
| 504 | 24 | PK | | | 60-0 | 21-61-61 | D04904P | | 17 | | | | D05988J | 32 | | 150-199, 275-299 |
| 505 | 24 | PK | | | 50-0 | 21-61-61 | D06734J | | 15 | | | | D05988J | 33 | | 050-099 |
| 505 | 24 | PK | | | 59-0 | 21-61-61 | D06734J | | 15 | | | | D05988J | 33 | | 150-199, 275-299 |
| 506 | 24 | PK | | | 50-0 | 21-61-61 | D04904P | | 19 | | | | D05988J | 34 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0940

Page 10

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | |
| 506 | 24 | | PK | 60-0 | 21-61-61 | D04904P | | 19 | | D05988J | | 34 | | 150-199, 275-299 | |
| 507 | 24 | | PK | 50-0 | 21-61-61 | D04904P | | 18 | | D05988J | | 35 | | 050-099 | |
| 507 | 24 | | PK | 60-0 | 21-61-61 | D04904P | | 18 | | D05988J | | 35 | | 150-199, 275-299 | |
| 508 | 24 | | PK | 50-0 | 21-61-71 | D04904P | | 52 | | D05988J | | 42 | | 050-099 | |
| 508 | 24 | | PK | 60-0 | 21-61-71 | D04904P | | 52 | | D05988J | | 42 | | 150-199, 275-299 | |
| 509 | 24 | | PK | 50-0 | 21-61-71 | D06734J | | 22 | | D05988J | | 43 | | 050-099 | |
| 509 | 24 | | PK | 59-0 | 21-61-71 | D06734J | | 22 | | D05988J | | 43 | | 150-199, 275-299 | |
| 510 | 24 | | PK | 50-0 | 21-61-71 | D06734J | | 23 | | D05988J | | 44 | | 050-099 | |
| 510 | 24 | | PK | 59-0 | 21-61-71 | D06734J | | 23 | | D05988J | | 44 | | 150-199, 275-299 | |
| 511 | 24 | | PK | 50-0 | 21-61-71 | D06734J | | 24 | | D05988J | | 45 | | 050-099 | |
| 511 | 24 | | PK | 59-0 | 21-61-71 | D06734J | | 24 | | D05988J | | 45 | | 150-199, 275-299 | |
| 512 | 24 | | PK | 28-0 | 21-26-31 | D06734J | | 25 | | D06658P | | 3 | | ALL | |
| 513 | 24 | | PK | 28-0 | 21-26-31 | D06734J | | 26 | | D06658P | | 2 | | ALL | |
| 514 | 24 | | PK | 28-0 | 21-26-31 | D06734J | | 27 | | D06658P | | 1 | | ALL | |
| 515 | 22 | | PQ | 60-0 | 21-26-31 | D13574 | U0 | 2 | | D06658P | | 4 | | 050-099 | |
| 515 | 22 | | PA | 72-0 | 21-26-31 | D13574 | | 2 | | D06658P | | 4 | | 150-154, 275 | |
| 515 | 22 | | PQ | 72-0 | 21-26-31 | D13574 | U0 | 2 | | D06658P | | 4 | | 155-199, 276-299 | |
| 515Z | | | U0 | 0-0 | 21-26-31 | D13574 | | DED | | D06658P | | DED | | 050-099, 155-199, 276-299 | |
| 516 | 22 | | PQ | 60-0 | 21-26-31 | D13574 | UP | 3 | | D06658P | | 5 | | 050-099 | |
| 516 | 22 | | PA | 72-0 | 21-26-31 | D13574 | | 3 | | D06658P | | 5 | | 150-154, 275 | |
| 516 | 22 | | PQ | 72-0 | 21-26-31 | D13574 | UP | 3 | | D06658P | | 5 | | 155-199, 276-299 | |
| 516Z | | | UP | 0-0 | 21-26-31 | D13574 | | DED | | D06658P | | DED | | 050-099, 155-199, 276-299 | |
| 517 | 22 | | PQ | 60-0 | 21-26-31 | D13574 | UQ | 4 | | D06658P | | 6 | | 050-099 | |
| 517 | 22 | | PA | 72-0 | 21-26-31 | D13574 | | 4 | | D06658P | | 6 | | 150-154, 275 | |
| 517 | 22 | | PQ | 72-0 | 21-26-31 | D13574 | UQ | 4 | | D06658P | | 6 | | 155-199, 276-299 | |
| 517Z | | | UQ | 0-0 | 21-26-31 | D13574 | | DED | | D06658P | | DED | | 050-099, 155-199, 276-299 | |
| 518 | 24 | | PK | 60-0 | 21-26-31 | D13574 | | 5 | | D06658P | | 7 | | 050-099 | |
| 518 | 24 | | PK | 72-0 | 21-26-31 | D13574 | | 5 | | D06658P | | 7 | | 150-199, 275-299 | |
| 519 | 20 | | PA | 23-0 | 21-26-31 | D13574 | | 7 | | GD03554 | S.. | 2 | | 050-099 | |
| 519 | 20 | | PA | 14-0 | 21-26-31 | D13574 | | 7 | | GD03554 | S.. | 2 | | 150-199, 275-299 | |
| 520 | 24 | | PK | 48-0 | 21-26-31 | D06734J | | 28 | | D13574 | | 6 | | 050-099 | |
| 520 | 24 | | PK | 60-0 | 21-26-31 | D06734J | | 28 | | D13574 | | 6 | | 150-199, 275-299 | |
| 521 | 24 | | PK | 28-0 | 21-28-11 | D06734J | | 33 | | D06658P | | 8 | | 050-099, 150-199, 275-276 | |
| 521 | 24 | | PK | 53-0 | 21-28-11 | D06734J | | 33 | | D13568 | | 8 | | 277-299 | |
| 522 | 24 | | PK | 28-0 | 21-28-11 | D06734J | | 34 | | D06658P | | 9 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0940

Page 11

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | | | |
| 523 | 24 | | PK | 28-0 | 21-28-11 | D06734J | | 35 | | | | | D06658P | 10 | | | ALL |
| 524 | 24 | | PK | 28-0 | 21-28-11 | D06734J | | 36 | | | | | D06658P | 11 | | | ALL |
| 525 | 24 | | PK | 28-0 | 21-28-11 | D06734J | | 37 | | | | | D06658P | 12 | | | ALL |
| 527 | 24 | | PK | 53-0 | 21-28-11 | D13562 | | 9 | | | | | D06734J | 32 | | | 050-099 |
| 527 | 24 | | PK | 61-0 | 21-28-11 | D13562 | | 9 | | | | | D06734J | 32 | | | 150-199, 275-299 |
| 528 | 24 | | PK | 53-0 | 21-28-11 | D13562 | | 7 | | | | | D06734J | 31 | | | 050-099 |
| 528 | 24 | | PK | 61-0 | 21-28-11 | D13562 | | 7 | | | | | D06734J | 31 | | | 150-199, 275-299 |
| 529 | 24 | | PK | 7-0 | 21-28-11 | D08004J | | 11 | | | | | D06734J | 30 | | | 050-099 |
| 529 | 24 | | PK | 8-0 | 21-28-11 | D08004J | | 11 | | | | | D06734J | 30 | | | 150-199, 275-299 |
| 530 | 24 | | PK | 7-0 | 21-28-11 | D08004J | | 12 | | | | | D06734J | 29 | | | 050-099 |
| 530 | 24 | | PK | 8-0 | 21-28-11 | D08004J | | 12 | | | | | D06734J | 29 | | | 150-199, 275-299 |
| 531 | 22 | | PA | 63-0 | 21-28-11 | D13562 | | 2 | | | | | D06658P | 14 | | | 050-099 |
| 531 | 22 | | PA | 73-0 | 21-28-11 | D13562 | | 2 | | | | | D06658P | 14 | | | 150-199, 275-299 |
| 532 | 20 | | PA | 17-0 | 21-28-11 | D13562 | | 3 | | | | | GD03554 | D.. | 2 | | 050-099 |
| 532 | 20 | | PA | 6-0 | 21-28-11 | D13562 | | 3 | | | | | GD03554 | D.. | 2 | | 150-199, 275-299 |
| 533 | 22 | | PA | 63-0 | 21-28-11 | D13562 | | 1 | | | | | D06658P | 15 | | | 050-099 |
| 533 | 22 | | PA | 73-0 | 21-28-11 | D13562 | | 1 | | | | | D06658P | 15 | | | 150-199, 275-299 |
| 534 | 20 | | PA | 17-0 | 21-28-11 | D13562 | | 5 | | | | | GD03554 | S.. | 2 | | 050-099 |
| 534 | 20 | | PA | 6-0 | 21-28-11 | D13562 | | 5 | | | | | GD03554 | S.. | 2 | | 150-199, 275-299 |
| 535 | 20 | | PA | 17-0 | 21-28-11 | D13562 | | 6 | | | | | GD03554 | D.. | 2 | | 050-099 |
| 535 | 20 | | PA | 6-0 | 21-28-11 | D13562 | | 6 | | | | | GD03554 | D.. | 2 | | 150-199, 275-299 |
| 536 | 20 | | PA | 17-0 | 21-28-11 | D13562 | | 8 | | | | | GD03554 | D.. | 2 | | 050-099 |
| 536 | 20 | | PA | 6-0 | 21-28-11 | D13562 | | 8 | | | | | GD03554 | D.. | 2 | | 150-199, 275-299 |
| 537 | 22 | | PQ | 23-0 | 21-28-11 | D06658P | VL | 16 | | | | | D08004J | 13 | | | 050-099 |
| 537 | 22 | | PA | 23-0 | 21-28-11 | D06658P | | 16 | | | | | D08004J | 13 | | | 150-199, 275-299 |
| 537Z | | | | 0-0 | 21-28-11 | D06658P | VL | DED | | | | | D08004J | DED | | | 050-099 |
| 538 | 22 | | PQ | 23-0 | 21-28-11 | D06658P | VM | 17 | | | | | D08004J | 14 | | | 050-099 |
| 538 | 22 | | PA | 23-0 | 21-28-11 | D06658P | | 17 | | | | | D08004J | 14 | | | 150-199, 275-299 |
| 538Z | | | | 0-0 | 21-28-11 | D06658P | VM | DED | | | | | D08004J | DED | | | 050-099 |
| 541 | 24 | | PK | 7-0 | 21-43-11 | D06734J | | 51 | | | | | D08004J | 15 | | | 050-099 |
| 541 | 24 | | PK | 8-0 | 21-43-11 | D06734J | | 51 | | | | | D08004J | 15 | | | 150-199, 275-299 |
| 542 | 24 | | PK | 27-0 | 21-43-11 | D06734J | | 52 | | | | | D06658P | 19 | | | 050-099 |
| 542 | 24 | | PK | 28-0 | 21-43-11 | D06734J | | 52 | | | | | D06658P | 19 | | | 150-199, 275-299 |
| 543 | 24 | | PK | 27-0 | 21-43-11 | D06734J | | 53 | | | | | D06658P | 20 | | | 050-099 |
| 543 | 24 | | PK | 28-0 | 21-43-11 | D06734J | | 53 | | | | | D06658P | 20 | | | 150-199, 275-299 |
| 544 | 24 | | PK | 27-0 | 21-43-11 | D06734J | | 54 | | | | | D06658P | 21 | | | 050-099 |
| 544 | 24 | | PK | 28-0 | 21-43-11 | D06734J | | 54 | | | | | D06658P | 21 | | | 150-199, 275-299 |
| 545 | 24 | | PK | 48-0 | 21-43-11 | D13596 | | 1 | | | | | D06734J | 55 | | | 050-099 |
| 545 | 24 | | PK | 57-0 | 21-43-11 | D13596 | | 1 | | | | | D06734J | 55 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0940

Page 12

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | |
| 546 | 20 | | PA | 15-0 | 21-43-11 | D13596 | | | 2 | | GD03554 | D.. | 2 | | 050-099 |
| 546 | 20 | | PA | 6-0 | 21-43-11 | D13596 | | | 2 | | GD03554 | D.. | 2 | | 150-199, 275-299 |
| 552 | 24 | | PK | 28-0 | 21-61-81 | D06734J | | | 50 | | D08680P | | 13 | | ALL |
| 554 | 24 | | PK | 27-0 | 21-61-81 | D08680P | | | 2 | | D06754J | | 10 | | ALL |
| 555 | 24 | | PK | 27-0 | 21-61-81 | D08680P | | | 3 | | D06754J | | 11 | | ALL |
| 556 | 24 | | PK | 48-0 | 21-61-81 | D06754J | | | 8 | | D05988J | | 49 | | 050-099 |
| 556 | 24 | | PK | 61-0 | 21-61-81 | D06754J | | | 8 | | D05988J | | 49 | | 150-199, 275-299 |
| 557 | 24 | | PK | 61-0 | 21-61-81 | D08680P | | | 6 | | D05988J | | 50 | | 050-099 |
| 557 | 24 | | PK | 73-0 | 21-61-81 | D08680P | | | 6 | | D05988J | | 50 | | 150-199, 275-299 |
| 558 | 24 | | PK | 61-0 | 21-61-81 | D08680P | | | 7 | | D05988J | | 51 | | 050-099 |
| 558 | 24 | | PK | 73-0 | 21-61-81 | D08680P | | | 7 | | D05988J | | 51 | | 150-199, 275-299 |
| 559 | 24 | | PK | 61-0 | 21-61-81 | D08680P | | | 8 | | D05988J | | 52 | | 050-099 |
| 559 | 24 | | PK | 73-0 | 21-61-81 | D08680P | | | 8 | | D05988J | | 52 | | 150-199, 275-299 |
| 565 | 24 | | PK | 28-0 | 21-58-12 | D06734J | | | 47 | | D08680P | | 14 | | ALL |
| 568 | 24 | | PK | 30-0 | 21-43-11 | D04904P | | | 26 | | D06658P | | 22 | | ALL |
| 569 | 24 | | PK | 17-0 | 21-43-11 | D04904P | | | 27 | | D06754J | | 14 | | ALL |
| 575 | 22 | | PA | 6-0 | 21-61-81 | D05686J | | | 5 | | D08680P | | 24 | | 050-099, 151-199, 275-299 |
| 585 | 20 | | PA | 93-0 | 27-18-11 | D06970P | | | 1 | | D04594J | | 16 | | 155-157, 166-199, 277-299 |
| 586 | 20 | | PA | 93-0 | 27-18-11 | D06970P | | | 2 | | D04594J | | 17 | | 155-157, 166-199, 277-299 |
| 587 | 20 | | PA | 93-0 | 27-18-11 | D06970P | | | 3 | | D04594J | | 18 | | 155-157, 166-199, 277-299 |
| 588 | 20 | | PA | 94-0 | 27-18-11 | D06970P | | | 4 | | SP02638 | | 9 | | 155-157, 166-199, 277-299 |
| 589 | 20 | | PA | 94-0 | 27-18-11 | D06970P | | | 5 | | SP05088 | | 9 | | 155-157, 166-199, 277-299 |
| 590 | 20 | | PA | 94-0 | 27-18-11 | D06970P | | | 6 | | SP02642 | | 9 | | 155-157, 166-199, 277-299 |
| 591 | 22 | | PA | 54-0 | 21-28-11 | D13568 | | | 1 | | D04904P | | 23 | | 277-299 |
| 592 | 22 | | PA | 54-0 | 21-28-11 | D13568 | | | 2 | | D04904P | | 24 | | 277-299 |
| 593 | 20 | | PA | 9-0 | 21-28-11 | D13568 | | | 3 | | GD05682 | D.. | 2 | | 277-299 |
| 594 | 20 | | PA | 9-0 | 21-28-11 | D13568 | | | 5 | | GD05682 | S.. | 2 | | 277-299 |
| 595 | 24 | | PK | 5-0 | 21-28-11 | D13568 | | | 6 | | SP05298 | | 9 | | 277-299 |
| 596 | 24 | | PK | 5-0 | 21-28-11 | D13568 | | | 7 | | SP05300 | | 9 | | 277-299 |
| 597 | 20 | | PA | 9-0 | 21-28-11 | D13568 | | | 9 | | GD05682 | D.. | 2 | | 277-299 |
| 619 | 24 | | PK | 28-0 | 21-26-31 | D06658P | | | 23 | | D06734J | | 38 | | ALL |
| 620 | 22 | | PA | 28-0 | 21-26-31 | D06658P | | | 24 | | D06734J | | 46 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0940
Page 13
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0942 | 286T0942 | | | L AIR COND CONTROL,ANTISKID (continued) | | | | | | | | | | | |
| 801 | 20 | | PA | | 50-0 | SPARE | D04904P | | 56 | | D08042J | | 26 | | 050-099 |
| 801 | 20 | | PA | | 63-0 | SPARE | D04904P | | 56 | | D08042J | | 26 | | 150-199, 275-299 |
| 802 | 20 | | PA | | 50-0 | SPARE | D04904P | | 57 | | D08042J | | 27 | | 050-099 |
| 802 | 20 | | PA | | 63-0 | SPARE | D04904P | | 57 | | D08042J | | 27 | | 150-199, 275-299 |
| 806 | 24 | | PK | | 1-0 | SPARE | D06246P | A15 | \$D | | D06246P | CAP | Y | | ALL |
| 807 | 24 | | PK | | 12-0 | 32-42-11 | D06246P | A16 | \$D | | D04904P | | 2 | | ALL |
| 811R | 22 | | PH | | 34-7 | 26-18-22 | D06242P | B19 | \$D | | D08112P | | 21 | | ALL |
| A-A | | | | | 0-0 | 27-18-11 | M01150 | | B | | SP02638 | | | 9 | 155-157, 166-199, 277-299 |
| A-B | | | | | 0-0 | 27-18-11 | M01151 | | B | | SP02642 | | | 9 | 155-157, 166-199, 277-299 |
| W0944 | 286T0944 | | | AIR COND PACK NO.1 CONTROL | | | | | | | | | | | |
| 001 | 20 | | UA | | 19-6 | 21-51-11 | D00746 | | 1 | | D05058P | | 1 | | ALL |
| 002 | 18 | | UA | | 7-0 | 21-51-11 | D00746 | | 2 | DK | GD00814 | | S.. | N | ALL |
| 003 | 18 | | UA | | 6-0 | 21-51-11 | D00746 | | 3 | DK | GD00816 | | D.. | N | ALL |
| 004 | 20 | | UA | | 19-6 | 21-51-11 | D00748 | | 5 | | D05058P | | 2 | | ALL |
| 005 | 20 | | UA | | 19-6 | 21-51-11 | D00748 | | 1 | | D05058P | | 3 | | ALL |
| 006 | 18 | | UA | | 6-0 | 21-51-11 | D00748 | | 3 | DK | GD00816 | | D.. | N | ALL |
| 007 | 18 | | UA | | 7-0 | 21-51-11 | D00748 | | 2 | DK | GD00814 | | S.. | N | * ALL |
| 008 | 20 | | UA | | 20-0 | 21-51-11 | D02770 | | 2 | | D05058P | | 4 | | ALL |
| 009 | 18 | | UA | | 18-0 | 21-51-11 | D02770 | | 1 | DK | GD00816 | | D.. | N | 050-099 |
| 009 | 20 | | UA | | 20-0 | 21-51-11 | D02770 | | 1 | | D05058P | | 9 | | 150-199, 275-299 |
| 010 | 18 | | UA | | 7-0 | 21-51-11 | D01598 | | 2 | DK | GD00814 | | S.. | N | * ALL |
| 201B | 20 | | UB | A | 20-0 | 21-51-11 | D01598 | | 3 | | D05058P | | 10 | | ALL |
| 201R | 20 | | UB | A | 0-0 | 21-51-11 | D01598 | | 1 | | D05058P | | 11 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0940

Page 14 End

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0952 | 286T0952 | | | AIR COND PACK NO.2 VALVE,ISOLATION VALVE | | | | | | | | | | | |
| 010 | 20 | | UA | | 13-8 | 21-51-21 | D05136P | 15 | | | D00668 | 2 | | | ALL |
| 011 | 18 | | UA | | 4-3 | 21-51-21 | GD00472 | D.. | N | | D00668 | 1 | | | ALL |
| 012 | 18 | | UA | | 5-0 | 21-52-31 | SM00001 | | 9 | | GD00472 | D.. | N | | ALL |
| 013 | 20 | | UA | | 1-0 | 21-52-31 | D00726 | | B | | SM00001 | | 9 | | ALL |
| 015 | 18 | | UA | | 2-1 | 21-52-41 | D00734 | 12 | DK | | GD00462 | S.. | N | | ALL |
| 020 | 18 | | UA | | 5-0 | 21-52-31 | SM00002 | | 9 | | GD03728 | D.. | N | | ALL |
| 021 | 20 | | UA | | 1-0 | 21-52-31 | SM00002 | | 9 | | D01336 | B | | | ALL |
| 022 | 18 | | UA | | 5-0 | 21-52-31 | SM00003 | | 9 | | GD03728 | D.. | N | | ALL |
| 023 | 20 | | UA | | 1-0 | 21-52-31 | SM00003 | | 9 | | D01326 | B | | | ALL |
| 024 | 18 | | UA | | 5-0 | 21-52-31 | SM00004 | | 9 | | GD03728 | D.. | N | | ALL |
| 025 | 20 | | UA | | 1-0 | 21-52-31 | SM00004 | | 9 | | D01296 | B | | | ALL |
| 026 | 20 | | UA | | 23-10 | 21-51-21 | D05136P | 32 | | | D01562 | 2 | | | ALL |
| 027 | 18 | | UA | | 14-11 | 21-51-21 | D01562 | 1 | | | GD00472 | D.. | N | | ALL |
| 028 | 18 | | UA | | 6-7 | 21-51-22 | D01568 | 2 | DK | | GD00914 | S.. | N | | ALL |
| 029 | 18 | | UA | | 5-0 | 21-52-31 | SM00005 | | 9 | | GD03728 | D.. | N | | ALL |
| 030 | 20 | | UA | | 1-0 | 21-52-31 | SM00005 | | 9 | | D02142 | B | | | ALL |
| 031 | 18 | | UA | | 5-0 | 21-52-31 | SM00006 | | 9 | | GD00464 | D.. | N | | ALL |
| 032 | 20 | | UA | | 1-0 | 21-52-31 | SM00006 | | 9 | | D02154 | B | | | ALL |
| 033 | 20 | | UA | | 12-0 | 36-21-11 | D05136P | 11 | | | D10146 | 3 | | | ALL |
| 034 | 18 | | UA | | 2-11 | 36-21-11 | GD02618 | D.. | N | | D10146 | 4 | DK | | ALL |
| 035 | 18 | | UA | | 2-11 | 36-21-11 | GD02616 | S.. | N | | D10146 | 5 | DK | | ALL |
| 201B | 20 | UB | B | | 13-7 | 21-52-31 | D05136P | 29 | | | D00726 | A | | | ALL |
| 201R | 20 | UB | B | | 0-0 | 21-52-31 | D05136P | 28 | | | SM00001 | | 9 | | ALL |
| 202B | 20 | UB | C | | 20-6 | 21-52-41 | D05136P | 2 | | | D00734 | 2 | | | ALL |
| 202R | 20 | UB | C | | 0-0 | 21-52-41 | D05136P | 3 | | | D00734 | 1 | | | ALL |
| 203B | 20 | UB | E | | 24-0 | 21-51-22 | D05136P | 19 | | | D00736 | 1 | | | ALL |
| 203R | 20 | UB | E | | 0-0 | 21-51-22 | D05136P | 20 | | | D00736 | 2 | | | ALL |
| 204B | 20 | UB | F | | 22-7 | 21-51-22 | D05136P | 21 | | | D02830 | 1 | | | ALL |
| 204R | 20 | UB | F | | 0-0 | 21-51-22 | D05136P | 22 | | | D02830 | 2 | | | ALL |
| 205B | 20 | UB | G | | 12-0 | 36-21-11 | D05136P | 9 | | | D10146 | 2 | | | ALL |
| 205R | 20 | UB | G | | 0-0 | 36-21-11 | D05136P | 8 | | | D10146 | 1 | | | ALL |
| 206B | 20 | UB | H | | 20-6 | 21-52-41 | D05136P | 23 | | | D00734 | 9 | | | ALL |
| 206R | 20 | UB | H | | 0-0 | 21-52-41 | D05136P | 10 | | | D00734 | 8 | | | ALL |
| 207B | 20 | UB | J | | 23-8 | 21-52-31 | D05136P | 1 | | | D01336 | A | | | ALL |
| 207R | 20 | UB | J | | 0-0 | 21-52-31 | D05136P | 14 | | | SM00002 | | 9 | | ALL |
| 208B | 20 | UB | K | | 24-0 | 21-52-31 | D05136P | 37 | | | D01326 | A | | | ALL |
| 208R | 20 | UB | K | | 0-0 | 21-52-31 | D05136P | 38 | | | SM00003 | | 9 | | ALL |
| 209B | 20 | UB | L | | 23-10 | 21-52-31 | D05136P | 30 | | | D01296 | A | | | ALL |
| 209R | 20 | UB | L | | 0-0 | 21-52-31 | D05136P | 31 | | | SM00004 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0950

Page 1

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0952 | 286T0952 | | | AIR COND PACK NO.2 VALVE,ISOLATION VALVE (continued) | | | | | | | | | | | | |
| 210B | 20 | UB | M | 24-4 | 21-51-22 | D01568 | | 3 | | | D05136P | | 33 | | ALL | |
| 210R | 20 | UB | M | 0-0 | 21-51-22 | D01568 | | 1 | | | D05136P | | 34 | | ALL | |
| 211B | 20 | UB | N | 23-10 | 21-52-31 | D05136P | | 35 | | | D02142 | | A | | ALL | |
| 211R | 20 | UB | N | 0-0 | 21-52-31 | D05136P | | 36 | | | SM00005 | | | 9 | ALL | |
| 212B | 20 | UB | P | 18-11 | 21-52-31 | D05136P | | 39 | | | D02154 | | A | | ALL | |
| 212R | 20 | UB | P | 0-0 | 21-52-31 | D05136P | | 40 | | | SM00006 | | | 9 | ALL | |
| 301B | 20 | UC | A | 23-11 | 21-52-21 | D05136P | | 4 | | | D00724 | | 1 | | ALL | |
| 301R | 20 | UC | A | 0-0 | 21-52-21 | D05136P | | 5 | | | D00724 | | 3 | | ALL | |
| 301Y | 20 | UC | A | 0-0 | 21-52-21 | D05136P | | 6 | | | D00724 | | 5 | | ALL | |
| 302B | 20 | UC | D | 23-11 | 21-51-22 | D05136P | | 16 | | | D00724 | | 2 | | ALL | |
| 302R | 20 | UC | D | 0-0 | 21-51-22 | D05136P | | 17 | | | D00724 | | 4 | | ALL | |
| 302Y | 20 | UC | D | 0-0 | 21-51-22 | D05136P | | 18 | | | D00724 | | 6 | | ALL | |
| 401B | 20 | UD | I | 20-6 | 21-52-41 | D05136P | | 24 | | | D00734 | | 5 | | ALL | |
| 401G | 20 | UD | I | 0-0 | 21-52-41 | D05136P | | 25 | | | D00734 | | 4 | | ALL | |
| 401R | 20 | UD | I | 0-0 | 21-52-41 | D05136P | | 26 | | | D00734 | | 6 | | ALL | |
| 401Y | 20 | UD | I | 0-0 | 21-52-41 | D05136P | | 27 | | | D00734 | | 3 | | ALL | |
| W0958 | 286T0958 | | | FORWARD CARGO DOOR (HINGE)-LTS,SENSORS,DOOR CONTROL | | | | | | | | | | | | |
| 005 | 20 | 8R | | 11-0 | 52-34-11 | D04306P | | 14 | | | D06266P | | 14 | | ALL | |
| 009 | 20 | 8R | | 11-0 | 33-31-61 | D04306P | | 22 | | | D06266P | | 22 | | ALL | |
| 010 | 20 | 8R | | 11-0 | 33-31-61 | D04306P | | 23 | | | D06266P | | 23 | | ALL | |
| 011 | 20 | 8R | | 11-0 | 52-34-11 | D04306P | | 11 | | | D06266P | | 11 | | ALL | |
| 012 | 20 | 8R | | 11-0 | 52-34-11 | D04306P | | 12 | | | D06266P | | 12 | | ALL | |
| 013 | 20 | 8R | | 11-0 | 52-34-11 | D04306P | | 13 | | | D06266P | | 13 | | ALL | |
| 014 | 20 | 8R | | 11-0 | 52-34-11 | D04306P | | 15 | | | D06266P | | 15 | | ALL | |
| 015 | 20 | 8R | | 11-0 | 52-34-11 | D04306P | | 24 | | | D06266P | | 24 | | ALL | |
| 016 | 20 | 8R | | 11-0 | 52-34-11 | D04306P | | 16 | | | D06266P | | 16 | | ALL | |
| 017 | 20 | 8R | | 11-0 | 33-31-61 | D04306P | | 17 | | | D06266P | | 17 | | ALL | |
| 018 | 20 | 8R | | 11-0 | 33-31-61 | D04306P | | 18 | | | D06266P | | 18 | | ALL | |
| 020 | 20 | 8R | | 11-0 | 33-37-11 | D04306P | | 20 | | | D06266P | | 20 | | ALL | |
| 064 | 20 | 8R | | 11-0 | 33-37-11 | D04306P | | 21 | | | D06266P | | 21 | | ALL | |
| 202B | 24 | PL | B | 11-0 | 52-34-13 | D04306P | | 3 | | | D06266P | | 3 | | ALL | |
| 202R | 24 | PL | B | 0-0 | 52-34-13 | D04306P | | 4 | | | D06266P | | 4 | | ALL | |
| 203B | 24 | PL | C | 11-0 | 52-34-13 | D04306P | | 5 | | | D06266P | | 5 | | ALL | |
| 203R | 24 | PL | C | 0-0 | 52-34-13 | D04306P | | 6 | | | D06266P | | 6 | | ALL | |
| 204B | 24 | PL | D | 11-0 | 52-71-13 | D04306P | | 7 | | | D06266P | | 7 | | ALL | |
| 204R | 24 | PL | D | 0-0 | 52-71-13 | D04306P | | 8 | | | D06266P | | 8 | | ALL | |
| 205B | 24 | PL | E | 11-0 | 52-34-13 | D04306P | | 9 | | | D06266P | | 9 | | ALL | |
| 205R | 24 | PL | E | 0-0 | 52-34-13 | D04306P | | 10 | | | D06266P | | 10 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W0950

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|--|-------|----------|-------------|------|------|-----------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0958 | 286T0958 | | | FORWARD CARGO DOOR (HINGE)-LTS,SENSORS,DOOR CONTROL (continued) | | | | | | | | | | | |
| 206B | 24 | PL | F | | 11-0 | 52-71-13 | D04306P | | 1 | | D06266P | | 1 | | ALL |
| 206R | 24 | PL | F | | 0-0 | 52-71-13 | D04306P | | 2 | | D06266P | | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W0950
Page 3 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0960 | 286T0960 | | | FWD CARGO DOOR-LTS,SENSORS,DOOR CONTROL | | | | | | | | | | | | |
| 001 | 20 | PA | | | 3-0 | 52-34-11 | SM00001 | | 9 | | | D01996 | 1 | | | 050-099 |
| 001 | 20 | PA | | | 3-0 | 52-34-11 | D01996 | | 1 | | | SM00001 | | 9 | | 150-199, 275-299 |
| 002 | 20 | PA | | | 3-0 | 52-34-11 | SM00003 | | 9 | | | D01996 | 2 | | | 050-099 |
| 002 | 20 | PA | | | 3-0 | 52-34-11 | D01996 | | 2 | | | SM00003 | | 9 | | 150-199, 275-299 |
| 003 | 20 | PA | | | 3-0 | 52-34-11 | SM00002 | | 9 | | | D01996 | 3 | | | 050-099 |
| 003 | 20 | PA | | | 3-0 | 52-34-11 | D01996 | | 3 | | | SM00002 | | 9 | | 150-199, 275-299 |
| 004 | 20 | PA | | | 10-0 | 52-34-11 | SM00004 | | 9 | | | D01994 | 5 | | | 050-099 |
| 004 | 20 | PA | | | 10-0 | 52-34-11 | D01994 | | 5 | | | SM00004 | | 9 | | 150-199, 275-299 |
| 005 | 20 | PA | | | 3-0 | 52-34-11 | SM00001 | | 9 | | | D01996 | 5 | | | 050-099 |
| 005 | 20 | PA | | | 3-0 | 52-34-11 | D01996 | | 5 | | | SM00001 | | 9 | | 150-199, 275-299 |
| 006 | 20 | PA | | | 3-0 | 52-34-11 | SM00003 | | 9 | | | D01996 | 6 | | | 050-099 |
| 006 | 20 | PA | | | 3-0 | 52-34-11 | D01996 | | 6 | | | SM00003 | | 9 | | 150-199, 275-299 |
| 007 | 20 | PA | | | 3-0 | 52-34-11 | SM00002 | | 9 | | | D01996 | 7 | | | 050-099 |
| 007 | 20 | PA | | | 3-0 | 52-34-11 | D01996 | | 7 | | | SM00002 | | 9 | | 150-199, 275-299 |
| 008 | 20 | PA | | | 9-0 | 52-34-11 | D06266J | | 14 | | | SM00004 | | 9 | | ALL |
| 009 | 20 | PA | | | 9-0 | 33-31-61 | L00739 | =P | D | * | | D06266J | 22 | | | 050-099, 275-299 |
| 009 | 20 | PA | | | 9-0 | 33-31-61 | D06266J | | 22 | | | L00739 | =P | D | * | 150-199 |
| 010 | 20 | PA | | | 9-0 | 33-31-61 | L00739 | =G | D | * | | D06266J | 23 | | | 050-099, 275-299 |
| 010 | 20 | PA | | | 9-0 | 33-31-61 | D06266J | | 23 | | | L00739 | =G | D | * | 150-199 |
| 011 | 20 | PA | | | 9-0 | 52-34-11 | SM00001 | | 9 | | | D06266J | 11 | | | 050-099 |
| 011 | 20 | PA | | | 9-0 | 52-34-11 | D06266J | | 11 | | | SM00001 | | 9 | | 150-199, 275-299 |
| 012 | 20 | PA | | | 9-0 | 52-34-11 | SM00002 | | 9 | | | D06266J | 12 | | | 050-099 |
| 012 | 20 | PA | | | 9-0 | 52-34-11 | D06266J | | 12 | | | SM00002 | | 9 | | 150-199, 275-299 |
| 013 | 20 | PA | | | 9-0 | 52-34-11 | SM00003 | | 9 | | | D06266J | 13 | | | 050-099 |
| 013 | 20 | PA | | | 9-0 | 52-34-11 | D06266J | | 13 | | | SM00003 | | 9 | | 150-199, 275-299 |
| 014 | 20 | PA | | | 3-0 | 52-34-11 | D01996 | | 4 | | | SM00004 | | 9 | | ALL |
| 015 | 20 | PA | | | 4-0 | 52-34-11 | D06266J | | 15 | | | D01994 | 1 | | | ALL |
| 016 | 20 | PA | | | 4-0 | 52-34-11 | D06266J | | 16 | | | D01994 | 2 | | | ALL |
| 017 | 20 | PA | | | 9-0 | 33-31-61 | L00172 | =P | D | * | | D06266J | 17 | | | 050-099, 275-299 |
| 017 | 20 | PA | | | 9-0 | 33-31-61 | D06266J | | 17 | | | L00172 | =P | D | * | 150-199 |
| 018 | 20 | PA | | | 9-0 | 33-31-61 | L00172 | =G | D | * | | D06266J | 18 | | | 050-099, 275-299 |
| 018 | 20 | PA | | | 9-0 | 33-31-61 | D06266J | | 18 | | | L00172 | =G | D | * | 150-199 |
| 020 | 20 | PA | | | 4-0 | 33-37-11 | L00617 | =P | D | * | | D06266J | 20 | | | 050-099 |
| 020 | 18 | PA | | | 4-0 | 33-37-11 | L00617 | =P | D | * | | D06266J | 20 | DL | | 150-199, 275-299 |
| 021 | 20 | PA | | | 4-0 | 33-37-11 | L00617 | =G | D | * | | D06266J | 21 | | | 050-099 |
| 021 | 18 | PA | | | 4-0 | 33-37-11 | L00617 | =G | D | * | | D06266J | 21 | DL | | 150-199, 275-299 |
| 022 | 20 | PA | | | 10-0 | 33-37-11 | L00618 | =P | D | | | L00617 | =P | D | * | 050-099 |
| 022 | 18 | PA | | | 10-0 | 33-37-11 | L00617 | =P | D | * | | L00618 | =P | D | | 150-199, 275-299 |
| 023 | 20 | PA | | | 10-0 | 33-37-11 | L00618 | =G | D | | | L00617 | =G | D | * | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0960

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|--|-------|-------------|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0960 | 286T0960 | FWD CARGO DOOR-LTS,SENSORS,DOOR CONTROL (continued) | | | | | | | | | | | | | |
| 023 | 18 | PA | | | 10-0 | 33-37-11 | L00617 | =G | D | * | L00618 | =G | D | | 150-199, 275-299 |
| 024 | 20 | PA | | | 4-0 | 52-34-11 | D06266J | | 24 | | D01994 | | 3 | | ALL |
| 025 | 20 | PA | | | 12-0 | 33-31-61 | L00740 | =P | D | | L00739 | =P | D | * | 050-099 |
| 025 | 20 | PA | | | 12-0 | 33-31-61 | L00739 | =P | D | * | L00740 | =P | D | | 150-199, 275-299 |
| 026 | 20 | PA | | | 12-0 | 33-31-61 | L00740 | =G | D | | L00739 | =G | D | * | 050-099 |
| 026 | 20 | PA | | | 12-0 | 33-31-61 | L00739 | =G | D | * | L00740 | =G | D | | 150-199, 275-299 |
| 027 | 20 | PA | | | 8-0 | 33-31-61 | L00173 | =P | D | | L00172 | =P | D | * | 050-099 |
| 027 | 20 | PA | | | 8-0 | 33-31-61 | L00172 | =P | D | * | L00173 | =P | D | | 150-199, 275-299 |
| 028 | 20 | PA | | | 8-0 | 33-31-61 | L00173 | =G | D | | L00172 | =G | D | * | 050-099 |
| 028 | 20 | PA | | | 8-0 | 33-31-61 | L00172 | =G | D | * | L00173 | =G | D | | 150-199, 275-299 |
| 202B | 24 | PL | B | | 10-0 | 52-34-13 | D06266J | | 3 | | SP00098 | | 9 | | ALL |
| 202R | 24 | PL | B | | 0-0 | 52-34-13 | D06266J | | 4 | | SP00100 | | 9 | | ALL |
| 203B | 24 | PL | C | | 11-0 | 52-34-13 | D06266J | | 5 | | SP00102 | | 9 | | ALL |
| 203R | 24 | PL | C | | 0-0 | 52-34-13 | D06266J | | 6 | | SP00104 | | 9 | | ALL |
| 204B | 24 | PL | D | | 11-0 | 52-71-13 | D06266J | | 7 | | SP00282 | | 9 | | ALL |
| 204R | 24 | PL | D | | 0-0 | 52-71-13 | D06266J | | 8 | | SP00284 | | 9 | | ALL |
| 205B | 24 | PL | E | | 13-0 | 52-34-13 | D06266J | | 9 | | SP00286 | | 9 | | ALL |
| 205R | 24 | PL | E | | 0-0 | 52-34-13 | D06266J | | 10 | | SP00288 | | 9 | | ALL |
| 206B | 24 | PL | F | | 17-0 | 52-71-13 | D06266J | | 1 | | SP00292 | | 9 | | ALL |
| 206R | 24 | PL | F | | 0-0 | 52-71-13 | D06266J | | 2 | | SP00290 | | 9 | | ALL |
| B-A | | | | | 0-0 | 52-34-13 | S00154 | | | BLU | SP00098 | | 9 | | ALL |
| B-B | | | | | 0-0 | 52-34-13 | S00154 | | | RED | SP00100 | | 9 | | ALL |
| C-A | | | | | 0-0 | 52-34-13 | S00150 | | | BLU | SP00102 | | 9 | | ALL |
| C-B | | | | | 0-0 | 52-34-13 | S00150 | | | RED | SP00104 | | 9 | | ALL |
| D-A | | | | | 0-0 | 52-71-13 | S00215 | | | BLU | SP00282 | | 9 | | ALL |
| D-B | | | | | 0-0 | 52-71-13 | S00215 | | | RED | SP00284 | | 9 | | ALL |
| E-A | | | | | 0-0 | 52-34-13 | S00152 | | | BLU | SP00286 | | 9 | | ALL |
| E-B | | | | | 0-0 | 52-34-13 | S00152 | | | RED | SP00288 | | 9 | | ALL |
| F-A | | | | | 0-0 | 52-71-13 | SP00290 | | 9 | | S00214 | | RED | | ALL |
| F-B | | | | | 0-0 | 52-71-13 | SP00292 | | 9 | | S00214 | | BLU | | ALL |
| W0962 | 286T0962 | AFT CARGO DOOR-LTS,SENSORS,DOOR CONTROL | | | | | | | | | | | | | |
| 010 | 20 | PA | | | 5-0 | 52-35-11 | D04314J | | 15 | | GD04602 | | S.. | E | ALL |
| 011 | 20 | PA | | | 7-0 | 52-35-11 | D02000 | | 1 | | D04314J | | 11 | | ALL |
| 012 | 20 | PA | | | 7-0 | 52-35-11 | D02000 | | 2 | | D04314J | | 12 | | ALL |
| 013 | 20 | PA | | | 7-0 | 52-35-11 | D02000 | | 3 | | D04314J | | 13 | | ALL |
| 014 | 20 | PA | | | 7-0 | 52-35-11 | D02000 | | 5 | | D04314J | | 14 | | ALL |
| 017 | 20 | PA | | | 7-0 | 33-31-61 | L00547 | =P | D | * | D04314J | | 17 | | 050-099, 275-299 |
| 017 | 20 | PA | | | 7-0 | 33-31-61 | D04314J | | 17 | | L00547 | =P | D | * | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W0960

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0962 | 286T0962 | | | AFT CARGO DOOR-LTS,SENSORS,DOOR CONTROL (continued) | | | | | | | | | | | | |
| 018 | 20 | PA | | 7-0 | 33-31-61 | L00547 | =G | D | * | D04314J | 18 | | | 050-099, 275-299 | | |
| 018 | 20 | PA | | 7-0 | 33-31-61 | D04314J | | 18 | | L00547 | =G | D | * | 150-199 | | |
| 020 | 20 | PA | | 7-0 | 33-37-21 | L00546 | =P | D | | D04314J | 20 | | | 050-099 | | |
| 020 | 18 | PA | | 7-0 | 33-37-21 | L00546 | =P | D | | D04314J | 19 | DL | | 150-199, 275-299 | | |
| 021 | 20 | PA | | 7-0 | 33-37-21 | L00546 | =G | D | | D04314J | 21 | | | 050-099 | | |
| 021 | 18 | PA | | 7-0 | 33-37-21 | L00546 | =G | D | | D04314J | 21 | DL | | 150-199, 275-299 | | |
| 027 | 20 | PA | | 6-0 | 33-31-61 | L00545 | =P | D | | L00547 | =P | D | * | 050-099 | | |
| 027 | 20 | PA | | 7-0 | 33-31-61 | L00547 | =P | D | * | L00545 | =P | D | | 150-199, 275-299 | | |
| 028 | 20 | PA | | 6-0 | 33-31-61 | L00545 | =G | D | | L00547 | =G | D | * | 050-099 | | |
| 028 | 20 | PA | | 7-0 | 33-31-61 | L00547 | =G | D | * | L00545 | =G | D | | 150-199, 275-299 | | |
| 202B | 24 | PL | B | 7-0 | 52-35-13 | D04314J | | 3 | | SP00076 | | | | ALL | | |
| 202R | 24 | PL | B | 0-0 | 52-35-13 | D04314J | | 4 | | SP00078 | | | | ALL | | |
| 203B | 24 | PL | C | 8-0 | 52-35-13 | D04314J | | 5 | | SP00080 | | | | ALL | | |
| 203R | 24 | PL | C | 0-0 | 52-35-13 | D04314J | | 6 | | SP00082 | | | | ALL | | |
| 204B | 24 | PL | D | 13-0 | 52-35-13 | D04314J | | 7 | | SP00084 | | | | ALL | | |
| 204R | 24 | PL | D | 0-0 | 52-35-13 | D04314J | | 8 | | SP00086 | | | | ALL | | |
| 205B | 24 | PL | E | 7-0 | 52-35-13 | D04314J | | 9 | | SP00088 | | | | 050-099 | | |
| 205R | 24 | PL | E | 0-0 | 52-35-13 | D04314J | | 10 | | SP00090 | | | | 050-099 | | |
| 206B | 24 | PL | F | 10-0 | 52-71-13 | D04314J | | 1 | | SP00304 | | | | ALL | | |
| 206R | 24 | PL | F | 0-0 | 52-71-13 | D04314J | | 2 | | SP00302 | | | | ALL | | |
| A-A | | | | 0-0 | 52-71-13 | S00208 | | | RED | SP00302 | | | | ALL | | |
| A-B | | | | 0-0 | 52-71-13 | S00208 | | | BLU | SP00304 | | | | ALL | | |
| B-A | | | | 0-0 | 52-35-13 | S00161 | | | BLU | SP00076 | | | | ALL | | |
| B-B | | | | 0-0 | 52-35-13 | S00161 | | | RED | SP00078 | | | | ALL | | |
| C-A | | | | 0-0 | 52-35-13 | S00157 | | | BLU | SP00080 | | | | ALL | | |
| C-B | | | | 0-0 | 52-35-13 | S00157 | | | RED | SP00082 | | | | ALL | | |
| D-A | | | | 0-0 | 52-35-13 | S00160 | | | BLU | SP00084 | | | | ALL | | |
| D-B | | | | 0-0 | 52-35-13 | S00160 | | | RED | SP00086 | | | | ALL | | |
| E-A | | | | 0-0 | 52-35-13 | S00159 | | | BLU | SP00088 | | | | 050-099 | | |
| E-B | | | | 0-0 | 52-35-13 | S00159 | | | RED | SP00090 | | | | 050-099 | | |
| W0964 | 286T0964 | | | AUTOBRAKE,BRAKE PRESS,ACHP PRESS SW #2 | | | | | | | | | | | | |
| 001 | 20 | UA | | 14-11 | 32-41-11 | D04954P | | 1 | | D01992 | | 1 | | ALL | | |
| 002 | 20 | UA | | 14-11 | 32-41-11 | D04954P | | 2 | | D01992 | | 2 | | ALL | | |
| 003 | 20 | UA | | 14-11 | 32-41-11 | D04954P | | 3 | | D01992 | | 3 | | ALL | | |
| 007 | 20 | UA | | 8-5 | 32-42-12 | D04954P | | 7 | | D02196 | | 2 | | ALL | | |
| 008 | 20 | UA | | 8-5 | 32-42-12 | D04954P | | 8 | | D02196 | | 1 | | ALL | | |
| 009 | 20 | UA | | 8-4 | 32-42-12 | D04954P | | 9 | | D02200 | | 2 | | ALL | | |
| 010 | 20 | UA | | 8-4 | 32-42-12 | D04954P | | 10 | | D02200 | | 3 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W0960

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|---|-------|------|-------------|----------|---------|------|------|---------|-------|------|------|---------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0964 | 286T0964 | AUTOBRAKE,BRAKE PRESS,ACHP PRESS SW #2 (continued) | | | | | | | | | | | | | |
| 012 | 20 | | UA | 8-10 | 32-42-12 | D04954P | | 12 | | D02202 | | 2 | | ALL | |
| 013 | 20 | | UA | 8-10 | 32-42-12 | D04954P | | 13 | | D02202 | | 1 | | ALL | |
| 014 | 18 | | UA | 10-5 | 29-11-31 | D04954P | | 14 | | D00476 | | 3 | | ALL | |
| 015 | 18 | | UA | 10-5 | 29-11-31 | D04954P | | 15 | | D00476 | | 2 | | ALL | |
| 018R | 18 | | XG | 3-3 | 26-17-11 | D04954P | | 18 | | D00946 | | =1 | | ALL | |
| 019R | 18 | | XG | 3-3 | 26-17-11 | D04954P | | 19 | | D00948 | | =1 | | ALL | |
| 201B | 20 | | PR | A | 9-9 | 32-42-12 | D04954P | | 5 | D02198 | | 2 | | ALL | |
| 201R | 20 | | PR | A | 0-0 | 32-42-12 | D04954P | | 6 | D02198 | | 1 | | ALL | |
| 201Z | 20 | | PR | A | 0-0 | 32-42-12 | D04954P | | 16 | D02198 | | DED | | ALL | |
| W0966 | 286T0966 | POTABLE WTR & LAV VACUUM WASTE SYSTEM | | | | | | | | | | | | | |
| 009 | 24 | | PK | 37-0 | 38-14-11 | D03446 | | 3 | | SP01466 | | | S | ALL | |
| 010 | 20 | | PA | 4-0 | 38-14-11 | D03446 | | 4 | | GD01890 | | D.. | E | 050-099 | |
| 010 | 20 | | PA | 3-0 | 38-14-11 | D03446 | | 4 | | GD01890 | | D.. | E | 150-199, 275-299 | |
| 011 | 20 | | PA | 4-0 | 38-14-11 | D03446 | | 5 | | GD01896 | | S.. | E | 050-099 | |
| 011 | 20 | | PA | 3-0 | 38-14-11 | D03446 | | 5 | | GD01896 | | S.. | E | 150-199, 275-299 | |
| 015 | 20 | | PA | 10-0 | 38-14-11 | D01176 | | 14 | | GD00054 | | S.. | 2 | 050-099 | |
| 015 | 20 | | PA | 9-0 | 38-14-11 | D01176 | | 14 | | GD00054 | | S.. | 2 | 150-199, 275-299 | |
| 019 | 20 | | PA | 4-0 | 38-14-11 | N00108 | | 3 | B | GD03920 | | S.. | E | 050-099, 164-199, 277-299 | |
| 019 | 20 | | PA | 2-7 | 38-14-11 | N00108 | | 3 | B | GD03920 | | S.. | E | 150-163, 275-276 | |
| 022 | 22 | | PA | 44-0 | 38-32-11 | SP00740 | | 9 | | SP00606 | | | S | 050-099, 164-199, 277-299 | |
| 022 | 22 | | PA | 43-8 | 38-32-11 | SP00740 | | 9 | | SP00606 | | | S | 150-163, 275-276 | |
| 023 | 20 | | PA | 68-0 | 38-32-11 | D01176 | | 22 | | D00612 | | CAP | Y | 050-099 | |
| 023 | 20 | | PA | 67-0 | 38-32-11 | D00612 | | 18 | Y | D01176 | | 22 | | 150-155, 162-165 | |
| 023 | 20 | | PA | 67-0 | 38-32-11 | D00612 | | 18 | | D01176 | | 22 | | 156-157, 166-199, 275-299 | |
| 025 | 20 | | PA | 10-0 | 38-32-11 | D01176 | | 8 | | GD00054 | | D.. | 2 | 050-099 | |
| 025 | 20 | | PA | 9-0 | 38-32-11 | D01176 | | 8 | | GD00054 | | D.. | 2 | 150-199, 275-299 | |
| 026 | 22 | | PA | 62-0 | 38-32-11 | SP01624 | | 9 | | D01176 | | 9 | | 050-099 | |
| 026 | 20 | | PA | 61-0 | 38-32-11 | SP01624 | | 9 | | D01176 | | 9 | | 150-199 | |
| 026 | 22 | | PA | 61-0 | 38-32-11 | SP01624 | | 9 | | D01176 | | 9 | | 275-299 | |
| 028 | 22 | | PA | 62-0 | 38-32-11 | D01176 | | 13 | | SP01626 | | | 9 | 050-099 | |
| 028 | 20 | | PA | 61-0 | 38-32-11 | D01176 | | 13 | | SP01626 | | | 9 | 150-199 | |
| 028 | 22 | | PA | 61-0 | 38-32-11 | D01176 | | 13 | | SP01626 | | | 9 | 275-299 | |
| 029 | 22 | | PA | 68-0 | 38-32-11 | D00612 | | 9 | | D01176 | | 12 | | 050-099 | |
| 029 | 22 | | PA | 67-0 | 38-32-11 | D00612 | | 9 | | D01176 | | 12 | | 150-199, 275-299 | |
| 030 | 20 | | PA | 3-0 | 38-32-11 | D00612 | | 7 | | SM00010 | | | 9 | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W0960

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0966 | 286T0966 | | | POTABLE WTR & LAV VACUUM WASTE SYSTEM (continued) | | | | | | | | | | | | | |
| 030 | 20 | | PA | 3-0 | 38-32-11 | D00612 | | 7 | | | | | GD03246 | D.. | E | | 150-154, 156-157, 275-276 |
| 030 | 20 | | PA | 2-0 | 38-32-11 | D00612 | | 7 | | | | | SM00010 | | 9 | | 155, 162-165 |
| 030 | 20 | | PA | 4-0 | 38-32-11 | D00612 | | 7 | | | | | GD03246 | D.. | E | | 166-199, 277-299 |
| 031 | 20 | | PA | 4-0 | 38-32-11 | D00612 | | 10 | | | | | GD03248 | S.. | E | | 050-099, 164-199, 277-299 |
| 031 | 20 | | PA | 3-0 | 38-32-11 | D00612 | | 10 | | | | | GD03248 | S.. | E | | 150-163, 275-276 |
| 033 | 22 | | PA | 68-0 | 38-32-11 | D00612 | | 8 | | | | | D01176 | 11 | | | 050-099 |
| 033 | 22 | | PA | 67-0 | 38-32-11 | D00612 | | 8 | | | | | D01176 | 11 | | | 150-199, 275-299 |
| 034 | 22 | | PA | 21-0 | 38-32-11 | D00612 | | 6 | | | | | SP00780 | | 9 | | 050-099, 164-199, 277-299 |
| 034 | 22 | | PA | 20-7 | 38-32-11 | D00612 | | 6 | | | | | SP00780 | | 9 | | 150-163, 275-276 |
| 036 | 20 | | PA | 10-0 | 38-32-11 | D01176 | | 10 | | | | | GD00054 | D.. | 2 | | 050-099 |
| 036 | 20 | | PA | 9-0 | 38-32-11 | D01176 | | 10 | | | | | GD00054 | D.. | 2 | | 150-199, 275-299 |
| 037 | 18 | | PA | 21-0 | 38-32-11 | D00612 | | 1 | DK | | | | SP00780 | | 9 | | 050-099, 164-199, 277-299 |
| 037 | 18 | | PA | 20-7 | 38-32-11 | D00612 | | 1 | DK | | | | SP00780 | | 9 | | 150-163, 275-276 |
| 039 | 18 | | PA | 44-0 | 38-32-11 | D00612 | | 2 | DK | | | | SP01700 | | S | | 050-099, 164-199, 277-299 |
| 039 | 18 | | PA | 43-10 | 38-32-11 | D00612 | | 2 | DK | | | | SP01700 | | S | | 150-163, 275-276 |
| 054 | 20 | | PA | 51-0 | 38-32-11 | D01176 | | 20 | | | | | SP00780 | | 9 | | 050-099 |
| 054 | 20 | | PA | 52-0 | 38-32-11 | SP00780 | | | 9 | | | | D01176 | 20 | | | 150-199, 277-299 |
| 054 | 20 | | PA | 46-0 | 38-32-11 | SP00780 | | | 9 | | | | D01176 | 20 | | | 275-276 |
| 055 | 20 | | PA | 68-0 | 38-32-11 | SM00008 | | | 9 | | | | D01176 | 21 | | | 050 |
| 055 | 20 | | PA | 46-0 | 38-32-11 | D01176 | | 21 | | | | | SM00008 | | 9 | | 051-099 |
| 055 | 20 | | PA | 67-0 | 38-32-11 | SM00008 | | | 9 | | | | D01176 | 21 | | | 150-154 |
| 055 | 20 | | PA | 45-0 | 38-32-11 | SM00008 | | | 9 | | | | D01176 | 21 | | | 155, 162-165 |
| 055 | 20 | | PA | 60-0 | 38-32-15 | SP05430 | | | 9 | | | | D01176 | 21 | | | 156, 166 |
| 055 | 20 | | PA | 50-0 | 38-32-15 | SP05430 | | | 9 | | | | D01176 | 21 | | | 157, 167-199, 277-299 |
| 055 | 20 | | PA | 69-0 | 38-32-14 | SP05442 | | | 9 | | | | D01176 | 21 | | | 275-276 |
| 056 | 20 | | PA | 62-0 | 38-32-11 | D01176 | | 19 | | | | | SP03636 | | 9 | | 050-099 |
| 056 | 20 | | PA | 61-0 | 38-32-11 | D01176 | | 19 | | | | | SP03636 | | 9 | | 150-199, 275-299 |
| 057 | 20 | | PQ | I | 62-0 | 38-32-11 | D01176 | | 17 | | | | SP00550 | | 9 | | 050-099 |
| 057 | 20 | | PA | | 61-0 | 38-32-11 | D01176 | | 17 | | | | SP00550 | | 9 | | 150-154 |
| 057 | 20 | | PQ | I | 61-0 | 38-32-11 | D01176 | | 17 | | | | SP00550 | | 9 | | 155-199, 275-299 |
| 057Z | | | | I | 0-0 | 38-32-11 | D01176 | | DED | | | | SP00550 | DED | | | 050-099, 155-199, 275-299 |
| 058 | 20 | | PQ | J | 62-0 | 38-32-11 | D01176 | | 18 | | | | SP00268 | | 9 | | 050-099 |
| 058 | 20 | | PA | | 61-0 | 38-32-11 | D01176 | | 18 | | | | SP00268 | | 9 | | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W0960

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0966 | 286T0966 | | | POTABLE WTR & LAV VACUUM WASTE SYSTEM (continued) | | | | | | | | | | | |
| 058 | 20 | PQ | J | | 61-0 | 38-32-15 | D01176 | | 18 | | SP00268 | | 9 | | 155, 157, 167-199, 277-299 |
| 058 | 20 | PQ | J | | 66-0 | 38-32-15 | D01176 | | 18 | | SP00268 | | 9 | | 156, 166 |
| 058 | 20 | PQ | J | | 61-0 | 38-32-11 | D01176 | | 18 | | SP00268 | | 9 | | 162-165 |
| 058 | 20 | PQ | J | | 61-0 | 38-32-14 | D01176 | | 18 | | SP00268 | | 9 | | 275-276 |
| 058Z | | | J | | 0-0 | 38-32-11 | D01176 | | DED | | SP00268 | DED | | | 050-099, 155, 162-165 |
| 058Z | | | J | | 0-0 | 38-32-15 | D01176 | | DED | | SP00268 | DED | | | 156-157, 166-199, 277-299 |
| 058Z | | | J | | 0-0 | 38-32-14 | D01176 | | DED | | SP00268 | DED | | | 275-276 |
| 060 | 20 | PA | | | 21-0 | 38-32-11 | SP03686 | | 9 | | D00612 | | 4 | | 050-099 |
| 060 | 20 | PA | | | 20-7 | 38-32-11 | D00612 | | 4 | | SP03686 | | 9 | | 155-163 |
| 060 | 20 | PA | | | 21-0 | 38-32-11 | D00612 | | 4 | | SP03686 | | 9 | | 164-199, 277-299 |
| 060 | 20 | PA | | | 21-0 | 38-32-14 | D00612 | | 4 | | SP03686 | | 9 | | 275 |
| 060 | 20 | PA | | | 20-7 | 38-32-14 | D00612 | | 4 | | SP03686 | | 9 | | 276 |
| 061 | 20 | PA | | | 3-0 | 38-32-11 | SM00010 | | 9 | | D00612 | | 11 | | 050-099 |
| 061 | 20 | PA | | | 2-0 | 38-32-11 | SM00010 | | 9 | | D00612 | | 11 | | 155, 162-165 |
| 073 | 20 | PA | | | 2-9 | 38-32-11 | D12214 | | 1 | | GD05850 | D.. | E | | 156-157 |
| 073 | 20 | PA | | | 4-0 | 38-32-11 | D12214 | | 1 | | GD05850 | D.. | E | | 166-199, 275-299 |
| 074 | 20 | PA | | | 2-9 | 38-32-11 | D12214 | | 2 | | GD05852 | S.. | E | | 156-157 |
| 074 | 20 | PA | | | 5-0 | 38-32-11 | D12214 | | 2 | | GD05852 | S.. | E | | 166-199, 275-299 |
| 075 | 22 | PA | | | 64-0 | 38-32-11 | D01176 | | 31 | | D12214 | | 4 | | 156-157, 166-199, 275-299 |
| 076 | 22 | PA | | | 64-0 | 38-32-11 | D01176 | | 30 | | D12214 | | 5 | | 156-157, 166-199, 275-299 |
| 077 | 22 | PA | | | 67-0 | 38-32-11 | D01176 | | 27 | | D00612 | | 12 | | 156-157, 166-199, 275-299 |
| 079 | 20 | PA | | | 68-0 | 38-32-11 | D01176 | | 25 | | GD03246 | D.. | E | | 156-157, 166-199, 275-299 |
| 080 | 22 | PQ | G | | 65-0 | 38-32-11 | D01176 | | 29 | | D12216 | | 4 | | 156-157, 166-199, 275-299 |
| 080Z | | | G | | 0-0 | 38-32-11 | D01176 | | DED | | D12216 | DED | | | 156-157, 166-199, 275-299 |
| 081 | 22 | PA | | | 65-0 | 38-32-11 | D01176 | | 28 | | D12216 | | 5 | | 156-157, 166-199, 275-299 |
| 082 | 22 | PQ | H | | 61-0 | 38-32-11 | D01176 | | 26 | | SP03986 | | S | | 156-157, 166-199 |
| 082 | 22 | PQ | H | | 61-0 | 38-32-11 | D01176 | | 26 | | SP03986 | | 9 | | 275-299 |
| 082Z | | | H | | 0-0 | 38-32-11 | D01176 | | DED | | SP03986 | DED | | | 156-157, 166-199, 275-299 |
| 083 | 20 | PA | | | 3-7 | 38-32-11 | D12216 | | 1 | | GD05850 | D.. | E | | 156-157 |

WIRE LIST
D280T132

91-21-11
Section W0960
Page 6
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0966 | 286T0966 | | | POTABLE WTR & LAV VACUUM WASTE SYSTEM (continued) | | | | | | | | | | | | |
| 083 | 20 | | PA | 5-0 | 38-32-11 | D12216 | | 1 | | | | | GD05850 | D.. | E | 166-199, 275-299 |
| 084 | 20 | | PA | 3-7 | 38-32-11 | D12216 | | 2 | | | | | GD05852 | S.. | E | 156-157 |
| 084 | 20 | | PA | 5-0 | 38-32-11 | D12216 | | 2 | | | | | GD05852 | S.. | E | 166-199, 275-299 |
| 086 | 22 | | PA | 30-0 | 38-32-11 | SP04046 | | | 9 | | | | SM00008 | | 9 | 050 |
| 086 | 22 | | PA | 24-0 | 38-32-11 | SP04046 | | | 9 | | | | SM00008 | | 9 | 051-099, 150-155, 162-165 |
| 086 | 22 | | PA | 50-0 | 38-32-15 | SP04046 | | | 9 | | | | SP05430 | | 9 | 156, 166 |
| 086 | 22 | | PA | 21-4 | 38-32-15 | SP04046 | | | 9 | | | | SP05430 | | 9 | 157 |
| 086 | 22 | | PA | 22-0 | 38-32-15 | SP04046 | | | 9 | | | | SP05430 | | 9 | 167-199, 277-299 |
| 086 | 22 | | PA | 69-0 | 38-32-14 | SP04046 | | | 9 | | | | SP05442 | | 9 | 275-276 |
| 087 | 22 | | PA | 30-0 | 38-32-11 | SP04048 | | | 9 | | | | GD01338 | D.. | E | 050 |
| 087 | 22 | | PA | 23-0 | 38-32-11 | SP04048 | | | 9 | | | | GD01338 | D.. | E | 051-099, 150-154, 164-165 |
| 087 | 22 | | PA | 22-11 | 38-32-11 | SP04048 | | | 9 | | | | GD01338 | D.. | E | 155, 162-163 |
| 087 | 22 | | PA | 22-11 | 38-32-15 | SP04048 | | | 9 | | | | GD01338 | D.. | E | 156 |
| 087 | 20 | | PA | 22-11 | 38-32-15 | SP04048 | | | 9 | | | | GD01338 | D.. | E | 157 |
| 087 | 22 | | PA | 23-0 | 38-32-15 | SP04048 | | | 9 | | | | GD01338 | D.. | E | 166 |
| 087 | 20 | | PA | 23-0 | 38-32-15 | SP04048 | | | 9 | | | | GD01338 | D.. | E | 167-199, 277-299 |
| 087 | 20 | | PA | 23-0 | 38-32-14 | SP04048 | | | 9 | | | | GD01338 | D.. | E | 275-276 |
| 088 | 22 | | PA | 22-0 | 38-32-11 | SP04050 | | | 9 | | | | SP00780 | | 9 | 050-099, 150-154, 164-165 |
| 088 | 22 | | PA | 21-4 | 38-32-11 | SP04050 | | | 9 | | | | SP00780 | | 9 | 155, 162-163 |
| 088 | 22 | | PA | 21-4 | 38-32-15 | SP04050 | | | 9 | | | | SP00780 | | 9 | 156-157 |
| 088 | 22 | | PA | 22-0 | 38-32-15 | SP04050 | | | 9 | | | | SP00780 | | 9 | 166-199, 277-299 |
| 088 | 22 | | PA | 30-0 | 38-32-14 | SP04050 | | | 9 | | | | SP00780 | | 9 | 275-276 |
| 089 | 20 | | PA | 30-0 | 38-32-11 | SM00008 | | | 9 | | | | D00612 | | 3 | 050 |
| 089 | 20 | | PA | 24-0 | 38-32-11 | SM00008 | | | 9 | | | | D00612 | | 3 | 051-099, 155, 162-165 |
| 089 | 20 | | PA | 30-0 | 38-32-11 | D00612 | | 3 | | | | | SM00008 | | 9 | 150-154 |
| 089 | 20 | | PA | 50-0 | 38-32-15 | SP05428 | | | 9 | | | | D00612 | | 3 | 156, 166 |
| 089 | 20 | | PA | 20-7 | 38-32-15 | SP05428 | | | 9 | | | | D00612 | | 3 | 157 |
| 089 | 20 | | PA | 21-0 | 38-32-15 | SP05428 | | | 9 | | | | D00612 | | 3 | 167-199, 277-299 |
| 089 | 20 | | PA | 100-0 | 38-32-14 | D00612 | | 3 | | | | | SP05444 | | 9 | 275-276 |
| 122 | 20 | | PA | 3-0 | 38-32-11 | SM00010 | | | 9 | | | | GD03246 | D.. | E | 050-099, 155, 162-165 |
| 202B | 24 | | PL B | 1-0 | 38-14-11 | D03446 | | 2 | | | | | SM00002 | | 9 | 050-099 |
| 202B | 24 | | PL B | 16-0 | 38-14-11 | D03446 | | 2 | | | | | SM00002 | | 9 | 150-199, 275-299 |
| 202R | 24 | | PL B | 0-0 | 38-14-11 | D03446 | | 1 | | | | | SM00001 | | 9 | ALL |
| 203B | 24 | | PL C | 61-0 | 38-14-11 | D01176 | | 7 | | | | | SM00002 | | 9 | 050-099 |
| 203B | 24 | | PL C | 45-0 | 38-14-11 | D01176 | | 7 | | | | | SM00002 | | 9 | 150-199, 277-299 |
| 203B | 24 | | PL AC | 45-0 | 38-14-11 | D01176 | | 7 | | | | | SM00002 | | 9 | 275-276 |

WIRE LIST

D280T132

91-21-11

Section W0960

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|--|----|-------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0966 | 286T0966 | POTABLE WTR & LAV VACUUM WASTE SYSTEM (continued) | | | | | | | | | | | | | |
| 203R | 24 | PL | C | 0-0 | 38-14-11 | D01176 | | 6 | | SM00001 | | 9 | | 050-099, 150-199, 277-299 | |
| 203R | 24 | PL | AC | 0-0 | 38-14-11 | D01176 | | 6 | | SM00001 | | 9 | | 275-276 | |
| 204B | 24 | PL | D | 86-0 | 38-14-11 | SM00002 | | 9 | | N00108 | | 2 | B | 050-099 | |
| 204B | 24 | PL | D | 44-2 | 38-14-11 | SM00002 | | 9 | | N00108 | | 2 | B | 150-163, 275-276 | |
| 204B | 24 | PL | D | 44-0 | 38-14-11 | SM00002 | | 9 | | N00108 | | 2 | B | 164-199, 277-299 | |
| 204R | 24 | PL | D | 0-0 | 38-14-11 | SM00001 | | 9 | | N00108 | | 1 | B | ALL | |
| 501 | 22 | PQ | M | 100-0 | 38-32-14 | SP05398 | | 9 | | SP00550 | | 9 | | 275-276 | |
| 501Z | | | M | 0-0 | 38-32-14 | SP05398 | DED | | | SP00550 | DED | | | 275-276 | |
| 502 | 22 | PA | | 100-0 | 38-32-14 | SP05400 | | 9 | | SP05402 | | 9 | | 275-276 | |
| A-F | | | | 0-0 | 38-32-11 | L01204 | | RED | | SP04046 | | 9 | | 050-099, 150-155, 162-165 | |
| A-F | | | | 0-0 | 38-32-15 | L01204 | | RED | | SP04046 | | 9 | | 156-157, 166-199, 277-299 | |
| A-F | | | | 0-0 | 38-32-14 | L01204 | | RED | | SP04046 | | 9 | | 275-276 | |
| A-G | | | | 0-0 | 38-32-11 | L01204 | | WHT | | SP04050 | | 9 | | 050-099, 150-155, 162-165 | |
| A-G | | | | 0-0 | 38-32-15 | L01204 | | WHT | | SP04050 | | 9 | | 156-157, 166-199, 277-299 | |
| A-G | | | | 0-0 | 38-32-14 | L01204 | | WHT | | SP04050 | | 9 | | 275-276 | |
| A-H | | | | 0-0 | 38-32-11 | L01204 | | BLK | | SP04048 | | 9 | | 050-099, 150-155, 162-165 | |
| A-H | | | | 0-0 | 38-32-15 | L01204 | | BLK | | SP04048 | | 9 | | 156-157, 166-199, 277-299 | |
| A-H | | | | 0-0 | 38-32-14 | L01204 | | BLK | | SP04048 | | 9 | | 275-276 | |
| B-A | | | | 0-0 | 38-32-11 | S00353 | | RED | | SP00738 | | 9 | | ALL | |
| B-B | | | | 0-0 | 38-32-11 | S00353 | | BLU | | SP00740 | | 9 | | ALL | |
| W0968 | 286T0968 | HYD SYS C QTY AND TEMP XMTR | | | | | | | | | | | | | |
| 001 | 18 | UA | | 10-3 | 29-32-11 | D04946P | | 4 | | D00552 | | 1 | | ALL | |
| 003 | 18 | UA | | 10-3 | 29-32-11 | D04946P | | 5 | | D00552 | | 2 | | ALL | |
| 004 | 20 | UA | | 11-0 | 29-33-11 | D04946P | | 2 | | D00556 | | 2 | | ALL | |
| 007 | 20 | VF | A | 11-0 | 29-33-11 | D04946P | | 7 | | D00556 | | 7 | | ALL | |
| 007Z | | | A | 0-0 | 29-33-11 | D04946P | | | FB | D00556 | | | FA | ALL | |
| 008 | 20 | UA | | 11-0 | 29-33-11 | D04946P | | 3 | | D00556 | | 5 | | ALL | |
| 009 | 20 | UA | | 11-0 | 29-33-11 | D04946P | | 9 | | D00556 | | 3 | | ALL | |
| 010 | 20 | UA | | 11-0 | 29-33-11 | D04946P | | 10 | | D00556 | | 4 | | ALL | |
| 011 | 20 | UA | | 0-7 | 29-33-11 | D00556 | | | FA | D00556 | | 1 | | ALL | |
| 012 | 18 | 5A | | 10-9 | 29-32-11 | D00552 | | 3 | | GD04040 | | S.. | N | ALL | |

WIRE LIST
D280T132

91-21-11
Section W0960
Page 8
Mar 09/2006



| Bundle No. | Part Number | | | Description | | | From | | | To | | | |
|--------------|-----------------|--|--|--|----------|---------|-------|------|------|---------|-------|------|------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type |
| W0968 | 286T0968 | | | HYD SYS C QTY AND TEMP XMTR (continued) | | | | | | | | | |
| FRA | | | | 0-0 | 29-33-11 | D00556 | | | FA | D00556 | 6 | | ALL |
| FRB | | | | 0-0 | 29-33-11 | D04946P | | | FB | D04946P | 1 | | ALL |
| FRC | | | | 0-0 | 29-33-11 | D04946P | | | FB | D04946P | 6 | | ALL |
| FRD | | | | 0-0 | 29-33-11 | D04946P | | | FB | D04946P | 8 | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0974 | 286T0974 | | | RAIN REPELLENT,WINDSHIELD WIPERS-L | | | | | | | | | | | |
| 001 | 22 | | PA | | 10-3 | 30-43-11 | D00564 | | | | D04704P | 1 | | | ALL |
| 002 | 20 | | PA | | 11-0 | 30-43-11 | D00564 | | | | GD00057 | D.. | 2 | | ALL |
| 003 | 20 | | PA | | 11-0 | 30-43-11 | D00564 | | | | GD00057 | S.. | 2 | | ALL |
| 007 | 18 | | PA | | 10-3 | 30-42-11 | D00562 | | | | D04704P | | 7 | | ALL |
| 008 | 18 | | PA | | 10-3 | 30-42-11 | D00562 | | | | D04704P | | 10 | | ALL |
| 009 | 16 | | PA | | 11-0 | 30-42-11 | D00562 | | | | GD00057 | D.. | 2 | | ALL |
| 011 | 16 | | PA | | 11-0 | 30-42-11 | GD00057 | | S.. | 2 | D00562 | | 6 | | ALL |
| 012 | 16 | | PA | | 10-3 | 30-42-11 | D04704P | | | | D00562 | | 1 | | ALL |
| W0976 | 286T0976 | | | RAIN REPELLENT,WINDSHIELD WIPERS-R | | | | | | | | | | | |
| 001 | 22 | | PA | | 10-0 | 30-43-11 | D00572 | | | | D04706P | | 1 | | ALL |
| 002 | 20 | | PA | | 12-0 | 30-43-11 | D00572 | | | | GD00073 | D.. | 2 | | ALL |
| 003 | 20 | | PA | | 12-0 | 30-43-11 | D00572 | | | | GD00073 | S.. | 2 | | ALL |
| 007 | 18 | | PA | | 10-0 | 30-42-11 | D00570 | | | | D04706P | | 7 | | ALL |
| 008 | 18 | | PA | | 10-0 | 30-42-11 | D00570 | | | | D04706P | | 10 | | ALL |
| 009 | 16 | | PA | | 12-0 | 30-42-11 | D00570 | | | | GD00073 | D.. | 2 | | ALL |
| 011 | 16 | | PA | | 12-0 | 30-42-11 | D00570 | | | | GD00073 | S.. | 2 | | ALL |
| 012 | 16 | | PA | | 10-0 | 30-42-11 | D04706P | | | | D00570 | | 1 | | ALL |
| W0978 | 286T0978 | | | OUTFLOW VALVE L | | | | | | | | | | | |
| 001 | 20 | | PA | | 7-0 | 21-31-11 | D00704 | | | | GD04712 | S.. | E | | 050-099 |
| 001 | 20 | | PA | | 5-0 | 21-31-11 | D00704 | | | | GD04712 | S.. | E | | 150-199, 275-299 |
| 002 | 20 | | PA | | 102-0 | 21-44-21 | D04698P | | | | D00566 | | 1 | | 050-099 |
| 002 | 20 | | PA | | 112-0 | 21-44-21 | D04698P | | | | D00566 | | 1 | | 150-199, 275-299 |
| 003 | 20 | | PA | | 5-0 | 21-44-21 | D00566 | | | | GD03564 | D.. | E | | 050-099 |
| 003 | 20 | | PA | | 4-0 | 21-44-21 | D00566 | | | | GD03564 | D.. | E | | 150-199, 275-299 |
| 004 | 20 | | PA | | 0-6 | 21-44-22 | D01850 | | | | SM00001 | | S | | 050-099 |
| 004 | 20 | | PA | | 1-0 | 21-44-22 | D01850 | | | | SM00001 | | S | | 150-199 |
| 005 | 20 | | PA | | 5-0 | 21-44-22 | GD03836 | | D.. | E | SM00001 | | S | | 050-099 |
| 005 | 20 | | PA | | 4-0 | 21-44-22 | SM00001 | | | S | GD03836 | D.. | E | | 150-199 |
| 201B | 24 | | PL | B | 85-0 | 21-31-11 | D04698P | | | | D00704 | | 6 | | 050-099 |
| 201B | 24 | | PL | B | 95-0 | 21-31-11 | D04698P | | | | D00704 | | 6 | | 150-199, 275-299 |
| 201R | 24 | | PL | B | 0-0 | 21-31-11 | D04698P | | | | D00704 | | 5 | | ALL |
| 202B | 24 | | PL | C | 85-0 | 21-31-21 | D04698P | | | | D00704 | | 9 | | 050-099 |
| 202B | 24 | | PL | C | 95-0 | 21-31-21 | D04698P | | | | D00704 | | 9 | | 150-199, 275-299 |
| 202R | 24 | | PL | C | 0-0 | 21-31-21 | D04698P | | | | D00704 | | 8 | | ALL |
| 203B | 20 | | PB | IC | 102-0 | 21-44-22 | D04698P | | | | SM00001 | | S | | 050-099 |
| 203B | 20 | | PB | D | 112-0 | 21-44-22 | D04698P | | | | SM00001 | | S | | 150-199 |
| 203R | 20 | | PB | IC | 0-0 | 21-44-22 | D01850 | | | A | D04698P | | 1 | | 050-099 |

WIRE LIST

D280T132

91-21-11
Section W0970
Page 1
Mar 09/2006



| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|------------------------------------|-------|----------|---------|------|------|--------|--------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0978 | 286T0978 | | | OUTFLOW VALVE L (continued) | | | | | | | | | | | |
| 203R | 20 | PB | D | | 0-0 | 21-44-22 | D04698P | | 1 | | D01850 | | A | | 150-199 |
| 301B | 22 | PC | A | | 4-6 | 21-31-31 | SP01926 | | | 9 | D00704 | | 3 | | 050-099 |
| 301B | 22 | PC | A | | 4-0 | 21-31-31 | SP01926 | | | 9 | D00704 | | 3 | | 150-199, 275-299 |
| 301R | 22 | PC | A | | 0-0 | 21-31-31 | SP01928 | | | 9 | D00704 | | 2 | | ALL |
| 301Y | 22 | PC | A | | 0-0 | 21-31-31 | SP01930 | | | 9 | D00704 | | 1 | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|---|-------|------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0980 | 286T0980 | CARGO HT-FWD FLOW CONTROL VALVE | | | | | | | | | | | | | | | |
| 006 | 18 | UA | | 22-0 | 33-31-21 | D04620P | | 4 | | | | | S00362 | 2 | C | | ALL |
| 007 | 18 | UA | | 2-0 | 33-31-21 | S00362 | | 3 | C | | | | SP00508 | | 9 | | ALL |
| 008 | 18 | UA | | 30-0 | 33-31-21 | SP00510 | | | 9 | | | | SP00508 | | 9 | | ALL |
| A-A | | | | 0-0 | 33-31-21 | SP00508 | | | 9 | | | | L00133 | BLK | | | ALL |
| A-B | | | | 0-0 | 33-31-21 | L00133 | | | WHT | | | | GD00470 | A.. | N | | ALL |
| A-C | | | | 0-0 | 33-31-21 | SP00510 | | | 9 | | | | L00134 | BLK | | | ALL |
| A-D | | | | 0-0 | 33-31-21 | L00134 | | | WHT | | | | GD00772 | A.. | N | | ALL |
| W0982 | 286T0982 | CARGO HT-FWD SHUTOFF VALVE | | | | | | | | | | | | | | | |
| 001 | 20 | UA | | 29-0 | 21-43-11 | D04636P | | 1 | | | | | D02764 | 2 | | | ALL |
| 002 | 20 | UA | | 29-0 | 21-43-11 | D04636P | | 2 | | | | | D02764 | 1 | | | ALL |
| 003 | 18 | UA | | 4-0 | 21-43-11 | D02764 | | 3 | | | | | GD00774 | A.. | N | | ALL |
| 004 | 18 | UA | | 5-0 | 21-43-11 | D02764 | | 5 | | | | | GD00776 | D.. | N | | ALL |
| 005 | 20 | UA | | 29-0 | 21-43-11 | D02764 | | 4 | | | | | D04636P | 8 | | | ALL |
| 006 | 20 | UA | | 21-0 | 21-51-21 | D04636P | | 3 | | | | | D01272 | 1 | | | ALL |
| 007 | 18 | UA | | 3-0 | 21-51-21 | GD00462 | | S.. | N | | | | D01272 | 2 | DK | | ALL |
| 008 | 18 | UA | | 4-0 | 21-51-21 | GD00464 | | D.. | N | | | | D01272 | 3 | DK | | ALL |
| 009 | 20 | UA | | 21-0 | 21-51-21 | D04636P | | 4 | | | | | D01278 | 5 | | | ALL |
| 010 | 18 | UA | | 4-0 | 21-51-21 | GD00464 | | D.. | N | | | | D01278 | 3 | DK | | ALL |
| 011 | 20 | UA | | 21-0 | 21-51-21 | D04636P | | 5 | | | | | D01278 | 1 | | | ALL |
| 012 | 18 | UA | | 3-0 | 21-51-21 | GD00462 | | S.. | N | * | | | D01278 | 2 | DK | | ALL |
| 013 | 18 | HL | | 5-0 | 21-51-21 | GD00464 | | D.. | N | | | | D01276 | 1 | DK | | 050-099 |
| 013 | 20 | HA | | 21-0 | 21-51-21 | D01276 | | 1 | | | | | D04636P | 7 | | | 150-199, 275-299 |
| 014 | 20 | HA | | 21-0 | 21-51-21 | D04636P | | 6 | | | | | D01276 | 2 | | | ALL |
| 015 | 18 | UA | | 5-0 | 21-51-21 | D01602 | | 2 | DK | | | | GD00462 | S.. | N | * | ALL |
| 016 | 20 | UA | | 29-0 | 21-43-11 | D02764 | | 6 | | | | | D04636P | 11 | | | ALL |
| 017 | 18 | UA | | 5-0 | 21-43-11 | D02764 | | 7 | | | | | GD00776 | D.. | N | | ALL |
| 201B | 20 | UB | C | 22-0 | 21-51-21 | D01602 | | 3 | | | | | D04636P | 9 | | | ALL |
| 201R | 20 | UB | C | 0-0 | 21-51-21 | D01602 | | 1 | | | | | D04636P | 10 | | | ALL |
| W0984 | 286T0984 | P4 TO L WING/BODY DISC-CABIN PRESS SYS | | | | | | | | | | | | | | | |
| 001 | 20 | PA | | 78-9 | 21-31-31 | D08054P | | 1 | | | | | D08060J | 1 | | | 050-099 |
| 001 | 20 | PA | | 88-9 | 21-31-31 | D08054P | | 1 | | | | | D08060J | 1 | | | 150-199, 275-299 |
| 002 | 20 | PA | | 78-9 | 21-31-31 | D08054P | | 2 | | | | | D08060J | 2 | | | 050-099 |
| 002 | 20 | PA | | 88-9 | 21-31-31 | D08054P | | 2 | | | | | D08060J | 2 | | | 150-199, 275-299 |
| 003 | 24 | PK | | 18-0 | 21-58-16 | D03060 | | 5 | | | | | D05654P | 8 | | | ALL |
| 004 | 24 | PK | | 18-0 | 21-58-16 | D03060 | | 6 | | | | | D05654P | 1 | | | ALL |
| 005 | 24 | PK | | 18-0 | 21-58-16 | D03060 | | 7 | | | | | D05654P | 2 | | | ALL |
| 006 | 20 | PA | | 5-0 | 21-58-16 | D03060 | | 8 | | | | | GD01206 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W0980
 Page 1
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0984 | 286T0984 | | | P4 TO L WING/BODY DISC-CABIN PRESS SYS (continued) | | | | | | | | | | | | | |
| 007 | 24 | | PK | 18-0 | 21-58-16 | D03060 | | | 9 | | | | D05654P | | 3 | | ALL |
| 008 | 24 | | PK | 18-0 | 21-58-16 | D03060 | | | 10 | | | | D05654P | | 4 | | ALL |
| 009 | 24 | | PK | 18-0 | 21-58-16 | D03060 | | | 11 | | | | D05654P | | 9 | | ALL |
| 010 | 20 | | PA | 5-0 | 21-58-16 | D03060 | | | 12 | | | | GD01206 | S.. | 2 | | ALL |
| 011 | 24 | | PK | 35-4 | 21-58-16 | D08054P | | | 3 | | | | D05654P | | 5 | | ALL |
| 012 | 22 | | PA | 14-0 | 21-58-16 | D05654P | | | 6 | | | | D10424 | | 2 | | ALL |
| 013 | 20 | | PA | 13-0 | 21-58-16 | D10424 | | | 1 | | | | GD01056 | D.. | 2 | | ALL |
| 301B | 22 | | PC | A | 78-9 | 21-31-31 | D08054P | | 4 | | | | D08060J | | 3 | | 050-099 |
| 301B | 22 | | PC | A | 88-9 | 21-31-31 | D08054P | | 4 | | | | D08060J | | 3 | | 150-199, 275-299 |
| 301R | 22 | | PC | A | 0-0 | 21-31-31 | D08054P | | 5 | | | | D08060J | | 4 | | ALL |
| 301Y | 22 | | PC | A | 0-0 | 21-31-31 | D08054P | | 6 | | | | D08060J | | 5 | | ALL |
| W0986 | 286T0986 | | | L AIR COND CONTROL | | | | | | | | | | | | | |
| 001 | 18 | | PA | 7-0 | 21-58-13 | D00654 | | | 8 | DK | | | GD04222 | S.. | E | | 050-099 |
| 001 | 18 | | PA | 7-3 | 21-58-13 | D00654 | | | 8 | DK | | | GD04222 | S.. | E | | 150-199, 275-299 |
| 002 | 24 | | PK | 28-0 | 21-58-13 | D00654 | | | 4 | | | | D08004P | | 3 | | 050-099 |
| 002 | 24 | | PK | 27-4 | 21-58-13 | D00654 | | | 4 | | | | D08004P | | 3 | | 150-199, 275-299 |
| 003 | 24 | | PK | 28-0 | 21-58-13 | D00654 | | | 2 | | | | D08004P | | 4 | | 050-099 |
| 003 | 24 | | PK | 27-4 | 21-58-13 | D00654 | | | 2 | | | | D08004P | | 4 | | 150-199, 275-299 |
| 004 | 24 | | PK | 28-0 | 21-58-13 | D00654 | | | 3 | | | | D08004P | | 5 | | 050-099 |
| 004 | 24 | | PK | 27-4 | 21-58-13 | D00654 | | | 3 | | | | D08004P | | 5 | | 150-199, 275-299 |
| 005 | 24 | | PK | 28-0 | 21-58-13 | D00654 | | | 5 | | | | D08004P | | 6 | | 050-099 |
| 005 | 24 | | PK | 27-4 | 21-58-13 | D00654 | | | 5 | | | | D08004P | | 6 | | 150-199, 275-299 |
| 006 | 20 | | PA | 7-0 | 21-58-13 | D00654 | | | 6 | | | | GD01208 | D.. | E | | 050-099 |
| 006 | 20 | | PA | 7-3 | 21-58-13 | D00654 | | | 6 | | | | GD01208 | D.. | E | | 150-199, 275-278 |
| 006 | 20 | | PA | 8-0 | 21-58-13 | D00654 | | | 6 | | | | GD01208 | D.. | E | | 280-299 |
| 007 | 20 | | PA | 7-0 | 21-58-13 | D00654 | | | 7 | | | | GD04224 | A.. | E | | 050-099 |
| 007 | 20 | | PA | 7-3 | 21-58-13 | D00654 | | | 7 | | | | GD04224 | A.. | E | | 150-199, 275-299 |
| 008 | 20 | | PA | 7-0 | 21-58-13 | D00654 | | | 1 | | | | GD01208 | D.. | E | | 050-099 |
| 008 | 20 | | PA | 7-3 | 21-58-13 | D00654 | | | 1 | | | | GD01208 | D.. | E | | 150-199, 275-299 |
| 025 | 12 | | PA | 14-0 | 21-58-14 | D06074P | | | 1 | | | | D00446 | | 1 | | ALL |
| 026 | 12 | | PA | 14-0 | 21-58-14 | D06074P | | | 2 | | | | D00446 | | 2 | | ALL |
| 027 | 12 | | PA | 14-0 | 21-58-14 | D06074P | | | 3 | | | | D00446 | | 3 | | ALL |
| 029 | 16 | | PA | 4-0 | 21-58-14 | D00446 | | | 7 | | | | GD03980 | S.. | 2 | | ALL |
| 030 | 18 | | PA | 14-0 | 21-58-14 | D06074P | | | 4 | | | | D00446 | | 5 | | ALL |
| 031 | 18 | | PA | 4-0 | 21-58-14 | D00446 | | | 6 | | | | GD03980 | D.. | 2 | | ALL |
| 032 | 24 | | PK | 27-0 | 21-58-11 | D08004P | | | 21 | | | | D00644 | | 1 | | ALL |
| 033 | 20 | | PA | 5-0 | 21-58-11 | D00644 | | | 2 | | | | GD04204 | D.. | E | | ALL |
| 034 | 20 | | PA | 4-0 | 21-58-12 | D03076 | | | 5 | | | | GD05412 | D.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W0980

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|--------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0986 | 286T0986 | | | L AIR COND CONTROL (continued) | | | | | | | | | | | |
| 034 | 20 | | PA | | 5-0 | 21-58-12 | D03076 | | 5 | | GD05412 | D.. | 2 | | 150-199, 275-299 |
| 035 | 24 | | PK | | 26-0 | 21-58-12 | D03076 | | 6 | | D08004P | | 22 | | ALL |
| 036 | 24 | | PV | E | 30-0 | 21-58-12 | D03076 | | 1 | | D06312P | | 1 | | 050-099 |
| 036 | 24 | | PV | E | 26-0 | 21-58-12 | D03076 | | 1 | | D06312P | | 1 | | 150-199, 275-299 |
| 036Z | | | | E | 0-0 | 21-58-12 | D03076 | | DED | | D06312P | DED | | | ALL |
| 037 | 24 | | PV | F | 30-0 | 21-58-12 | D03076 | | 2 | | D06312P | | 2 | | 050-099 |
| 037 | 24 | | PV | F | 26-0 | 21-58-12 | D03076 | | 2 | | D06312P | | 2 | | 150-199, 275-299 |
| 037Z | | | | F | 0-0 | 21-58-12 | D03076 | | DED | | D06312P | DED | | | ALL |
| 038 | 24 | | PK | | 26-0 | 21-58-12 | D03076 | | 7 | | D08004P | | 25 | | ALL |
| 039 | 20 | | PA | | 4-0 | 21-58-12 | D03076 | | 8 | | GD05412 | D.. | 2 | | 050-099 |
| 039 | 20 | | PA | | 5-0 | 21-58-12 | D03076 | | 8 | | GD05412 | D.. | 2 | | 150-199, 275-299 |
| 040 | 20 | | PQ | G | 4-0 | 21-58-12 | D03076 | | 3 | | GD05412 | A.. | 2 | | 050-099 |
| 040 | 20 | | PQ | G | 5-0 | 21-58-12 | D03076 | | 3 | | GD05412 | A.. | 2 | | 150-199, 275-299 |
| 040Z | | | | G | 0-0 | 21-58-12 | D03076 | | DED | | GD05412 | DED | | | ALL |
| 041 | 20 | | PA | | 4-0 | 21-58-12 | D03076 | | 4 | | GD05412 | S.. | 2 | | 050-099 |
| 041 | 20 | | PA | | 5-0 | 21-58-12 | D03076 | | 4 | | GD05412 | S.. | 2 | | 150-199, 275-299 |
| 050 | 20 | | PA | | 18-0 | 21-58-12 | D00652 | | 5 | | GD03980 | D.. | 2 | | 050-099 |
| 050 | 20 | | PA | | 16-0 | 21-58-12 | D00652 | | 5 | | GD03980 | D.. | 2 | | 150-199, 275-299 |
| 051 | 24 | | PK | | 28-0 | 21-58-12 | D00652 | | 6 | | D08004P | | 30 | | 050-099 |
| 051 | 24 | | PK | | 27-0 | 21-58-12 | D00652 | | 6 | | D08004P | | 30 | | 150-199, 275-299 |
| 052 | 24 | | PV | H | 29-0 | 21-58-12 | D00652 | | 1 | | D06312P | | 3 | | 050-099 |
| 052 | 24 | | PV | H | 27-0 | 21-58-12 | D00652 | | 1 | | D06312P | | 3 | | 150-199, 275-299 |
| 052Z | | | | H | 0-0 | 21-58-12 | D00652 | | DED | | D06312P | DED | | | ALL |
| 053 | 24 | | PV | I | 29-0 | 21-58-12 | D00652 | | 2 | | D06312P | | 4 | | 050-099 |
| 053 | 24 | | PV | I | 27-0 | 21-58-12 | D00652 | | 2 | | D06312P | | 4 | | 150-199, 275-299 |
| 053Z | | | | I | 0-0 | 21-58-12 | D00652 | | DED | | D06312P | DED | | | ALL |
| 054 | 24 | | PK | | 28-0 | 21-58-12 | D00652 | | 7 | | D08004P | | 33 | | 050-099 |
| 054 | 24 | | PK | | 27-0 | 21-58-12 | D00652 | | 7 | | D08004P | | 33 | | 150-199, 275-299 |
| 055 | 20 | | PA | | 18-0 | 21-58-12 | D00652 | | 8 | | GD03980 | D.. | 2 | | 050-099 |
| 055 | 20 | | PA | | 16-0 | 21-58-12 | D00652 | | 8 | | GD03980 | D.. | 2 | | 150-199, 275-299 |
| 056 | 20 | | PQ | J | 18-0 | 21-58-12 | D00652 | | 3 | | GD03980 | A.. | 2 | | 050-099 |
| 056 | 20 | | PQ | J | 16-0 | 21-58-12 | D00652 | | 3 | | GD03980 | A.. | 2 | | 150-199, 275-299 |
| 056Z | | | | J | 0-0 | 21-58-12 | D00652 | | DED | | GD03980 | DED | | | ALL |
| 057 | 20 | | PA | | 18-0 | 21-58-12 | D00652 | | 4 | | GD03980 | S.. | 2 | | 050-099 |
| 057 | 20 | | PA | | 16-0 | 21-58-12 | D00652 | | 4 | | GD03980 | S.. | 2 | | 150-199, 275-299 |
| 066 | 24 | | PK | | 22-0 | 21-28-11 | D13564 | | 9 | | D08004P | | 11 | | ALL |
| 067 | 24 | | PK | | 22-0 | 21-28-11 | D13564 | | 7 | | D08004P | | 12 | | ALL |
| 068 | 22 | | PQ | CR | 22-0 | 21-28-11 | D13564 | | 2 | | D08004P | | 13 | | 050-099 |
| 068 | 22 | | PA | | 22-0 | 21-28-11 | D13564 | | 2 | | D08004P | | 13 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W0980

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0986 | 286T0986 | | | L AIR COND CONTROL (continued) | | | | | | | | | | | |
| 068Z | | | CR | 0-0 | 21-28-11 | D13564 | | DED | | | D08004P | DED | | | 050-099 |
| 069 | 20 | PQ | CS | 9-0 | 21-28-11 | D13564 | | 3 | | | GD05684 | D.. | E | | 050-099 |
| 069 | 20 | PA | | 9-0 | 21-28-11 | D13564 | | 3 | | | GD05684 | D.. | E | | 150-199, 275-299 |
| 069Z | | | CS | 0-0 | 21-28-11 | D13564 | | DED | | | GD05684 | DED | | | 050-099 |
| 070 | 22 | PQ | CT | 22-0 | 21-28-11 | D13564 | | 1 | | | D08004P | 14 | | | 050-099 |
| 070 | 22 | PA | | 22-0 | 21-28-11 | D13564 | | 1 | | | D08004P | 14 | | | 150-199, 275-299 |
| 070Z | | | CT | 0-0 | 21-28-11 | D13564 | | DED | | | D08004P | DED | | | 050-099 |
| 071 | 20 | PA | | 9-0 | 21-28-11 | D13564 | | 5 | | | GD01384 | S.. | E | | ALL |
| 072 | 20 | PA | | 9-0 | 21-28-11 | D13564 | | 6 | | | GD05684 | D.. | E | | ALL |
| 073 | 20 | PA | | 9-0 | 21-28-11 | D13564 | | 8 | | | GD05684 | D.. | E | | ALL |
| 074 | 24 | PK | | 31-0 | 21-43-11 | D13594 | | 1 | | | D08004P | 15 | | | ALL |
| 075 | 20 | PA | | 13-0 | 21-43-11 | D13594 | | 2 | | | GD04170 | D.. | 2 | | ALL |
| 076 | 20 | PA | | 1-0 | 21-43-12 | SM00001 | | | S | | D13602 | B | | | ALL |
| 077 | 20 | PA | | 13-0 | 21-43-12 | SM00001 | | | S | | GD04170 | D.. | 2 | | ALL |
| 201B | 22 | PB | A | 53-0 | 21-51-12 | D02794 | | 1 | | | D08004P | 1 | | | 050-099 |
| 201B | 22 | PB | A | 63-0 | 21-51-12 | D02794 | | 1 | | | D08004P | 1 | | | 150-199, 275-299 |
| 201R | 22 | PB | A | 0-0 | 21-51-12 | D02794 | | 2 | | | D08004P | 2 | | | ALL |
| 204B | 24 | PL | ID | 31-0 | 21-61-81 | D13586 | | 1 | | | D08004P | 17 | | | ALL |
| 204R | 24 | PL | ID | 0-0 | 21-61-81 | D13586 | | 2 | | | D08004P | 16 | | | ALL |
| 205B | 20 | PB | IE | 31-0 | 21-43-12 | D08004P | | 18 | | | SM00001 | | S | | ALL |
| 205R | 20 | PB | IE | 0-0 | 21-43-12 | D08004P | | 19 | | | D13602 | A | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W0980

Page 4 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0998 | 286T0998 | | | OUTFLOW VALVE-CABIN PRESSURE SYSTEM | | | | | | | | | | | |
| 001 | 20 | | | PA | 84-0 | 21-31-31 | D08060P | | | | D00744 | | | | 050-099 |
| 001 | 20 | | | PA | 93-6 | 21-31-31 | D08060P | | | | D00744 | | | | 150-199, 275-299 |
| 002 | 20 | | | PA | 84-0 | 21-31-31 | D08060P | | | | D00744 | | | | 050-099 |
| 002 | 20 | | | PA | 93-6 | 21-31-31 | D08060P | | | | D00744 | | | | 150-199, 275-299 |
| 003 | 20 | | | PA | 7-0 | 21-31-31 | GD01490 | | D.. | 2 | D00744 | | | | ALL |
| 301B | 22 | | | PC | 84-0 | 21-31-31 | D08060P | | | | SP01926 | | | 9 | 050-099 |
| 301B | 22 | | | PC | 93-10 | 21-31-31 | D08060P | | | | SP01926 | | | 9 | 150-199, 275-299 |
| 301R | 22 | | | PC | 0-0 | 21-31-31 | D08060P | | | | SP01928 | | | 9 | ALL |
| 301Y | 22 | | | PC | 0-0 | 21-31-31 | D08060P | | | | SP01930 | | | 9 | ALL |

WIRE LIST
D280T132

91-21-11
Section W0990
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|--|-------|-----|-------------|---------|-------|-------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1002 | 286T1002 | P34-N1-APU/115VAC GND SVCE PWR FEEDER | | | | | | | | | | | | | | |
| 001 | 06 | | HA | 2-0 | 24-51-61 | C00905 | T1 | F5 | *1 | C00834 | 1 | F3 | | ALL | | |
| 002 | 06 | | HA | 2-0 | 24-51-61 | C00905 | T2 | F5 | *2 | C00835 | 1 | F3 | | ALL | | |
| 003 | 06 | | HA | 2-0 | 24-51-61 | C00905 | T3 | F5 | *3 | C00836 | 1 | F3 | | ALL | | |
| 004 | 08 | | PA | 2-0 | 24-51-52 | C00905 | T1 | F5 | *1 | C00322 | A1 | D | | ALL | | |
| 005 | 08 | | PA | 1-6 | 24-51-52 | C00905 | T2 | F5 | *2 | C00322 | B1 | D | | ALL | | |
| 006 | 08 | | PA | 1-6 | 24-51-52 | C00905 | T3 | F5 | *3 | C00322 | C1 | D | | ALL | | |
| W1003 | 286T1003 | SATCOM SYSTEM , E10 SHELF | | | | | | | | | | | | | | |
| 004 | 24 | | PK | 1-0 | 23-25-16 | D02651A | | D05 | | D02651A | B05 | | | 156-157, 166-199, 277-299 | | |
| 005 | 20 | | PA | 2-0 | 23-25-16 | D02651C | | 1 | | D06167J | 9 | | | 156-157, 166-199, 277-299 | | |
| 006 | 20 | | PA | 2-0 | 23-25-16 | D02651C | | 7 | | D06167J | 10 | | | 156-157, 166-199, 277-299 | | |
| 007 | 20 | | PA | 2-0 | 23-25-16 | D02651C | | 8 | | D06167J | 11 | | | 156-157, 166-199, 277-299 | | |
| 201B | 24 | | PW IA | 2-0 | 23-25-16 | D02651A | | D01 | | D06167J | 1 | | | 156-157, 166-199, 277-299 | | |
| 201R | 24 | | PW IA | 0-0 | 23-25-16 | D02651A | | C01 | | D06167J | 2 | | | 156-157, 166-199, 277-299 | | |
| 201Z | | | IA | 0-0 | 23-25-16 | D02651A | | DED | | D06167J | 3 | | | 156-157, 166-199, 277-299 | | |
| 202B | 24 | | PW IB | 2-0 | 23-25-16 | D02651A | | B01 | | D06167J | 4 | | | 156-157, 166-199, 277-299 | | |
| 202R | 24 | | PW IB | 0-0 | 23-25-16 | D02651A | | A01 | | D06167J | 5 | | | 156-157, 166-199, 277-299 | | |
| 202Z | | | IB | 0-0 | 23-25-16 | D02651A | | DED | | D06167J | 6 | | | 156-157, 166-199, 277-299 | | |
| 203B | 24 | | PL IC | 2-0 | 23-25-16 | D02651A | | CAP Y | | D06167J | 7 | | | 156-157, 166-199 | | |
| 203B | 24 | | PL IC | 2-0 | 23-25-16 | D02651A | | B03 | | D06167J | 7 | | | 277-299 | | |
| 203R | 24 | | PL IC | 0-0 | 23-25-16 | D02651A | | CAP Y | | D06167J | 8 | | | 156-157, 166-199 | | |
| 203R | 24 | | PL IC | 0-0 | 23-25-16 | D02651A | | A03 | | D06167J | 8 | | | 277-299 | | |
| 901B | 22 | | PB CC | 2-0 | 23-25-17 | D06167J | | 12 | | D02651A | B03 | | | 156-157, 166-199 | | |
| 901R | 22 | | PB CC | 0-0 | 23-25-17 | D06167J | | 13 | | D02651A | A03 | | | 156-157, 166-199 | | |
| 902B | 22 | | PB BL | 2-0 | 23-25-17 | D02651A | | D03 | | D06167J | 15 | | | 156-157, 166-199 | | |
| 902R | 22 | | PB BL | 0-0 | 23-25-17 | D02651A | | C03 | | D06167J | 14 | | | 156-157, 166-199 | | |
| W1004 | 286T1004 | P34-A1-115V AC-EP GND SVCR PWR DISTRIBUTION | | | | | | | | | | | | | | |
| 001 | 06 | | HA | 5-6 | 24-51-61 | K00101 | | A3 F3 | | C00834 | 2 | F3 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W1000

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1004 | 286T1004 | | | P34-A1-115V AC-EP GND SVCR PWR DISTRIBUTION (continued) | | | | | | | | | | | | |
| 002 | 06 | | HA | 5-0 | 24-51-61 | K00101 | B3 | F3 | | C00835 | 2 | F3 | | ALL | | |
| 003 | 06 | | HA | 5-0 | 24-51-61 | K00101 | C3 | F3 | | C00836 | 2 | F3 | | ALL | | |
| 004 | 08 | | PA | 5-0 | 24-51-52 | K00103 | A1 | F | | C00322 | A2 | D | | ALL | | |
| 005 | 08 | | PA | 5-0 | 24-51-52 | K00103 | B1 | F | | C00322 | B2 | D | | ALL | | |
| 006 | 08 | | PA | 5-0 | 24-51-52 | K00103 | C1 | F | | C00322 | C2 | D | | ALL | | |
| W1006 | 286T1006 | | | P34-N1-EP/115V AC GND SVCE PWR FEEDER | | | | | | | | | | | | |
| 001 | 06 | | HA | 1-6 | 24-51-61 | K00114 | A1 | F5 | *1 | C00831 | 1 | F3 | | ALL | | |
| 002 | 06 | | HA | 1-6 | 24-51-61 | K00114 | B1 | F5 | *2 | C00832 | 1 | F3 | | ALL | | |
| 003 | 06 | | HA | 1-6 | 24-51-61 | K00114 | C1 | F5 | *3 | C00833 | 1 | F3 | | ALL | | |
| 004 | 08 | | PA | 2-0 | 24-51-52 | K00114 | A1 | F5 | *1 | C00306 | A1 | D | | ALL | | |
| 005 | 08 | | PA | 2-0 | 24-51-52 | K00114 | B1 | F5 | *2 | C00306 | B1 | D | | ALL | | |
| 006 | 08 | | PA | 2-0 | 24-51-52 | K00114 | C1 | F5 | *3 | C00306 | C1 | D | | ALL | | |
| W1008 | 286T1008 | | | P34-N1-APU/115V AC GND SVCE PWR DISTRIBUTION | | | | | | | | | | | | |
| 001 | 06 | | HA | 4-0 | 24-51-61 | K00101 | A1 | F3 | | C00831 | 2 | F3 | | ALL | | |
| 002 | 06 | | HA | 4-0 | 24-51-61 | K00101 | B1 | F3 | | C00832 | 2 | F3 | | ALL | | |
| 003 | 06 | | HA | 3-6 | 24-51-61 | K00101 | C1 | F3 | | C00833 | 2 | F3 | | ALL | | |
| 004 | 08 | | PA | 4-0 | 24-51-52 | K00103 | A3 | F | | C00306 | A2 | D | | ALL | | |
| 005 | 08 | | PA | 3-6 | 24-51-52 | K00103 | B3 | F | | C00306 | B2 | D | | ALL | | |
| 006 | 08 | | PA | 3-6 | 24-51-52 | K00103 | C3 | F | | C00306 | C2 | D | | ALL | | |

WIRE LIST
D280T132

91-21-11
Section W1000
Page 2 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|--|----|-----|-------------|----------|---------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1010 | 286T1010 | P34-N1-115VAC GND HNDLG PWR BUS | | | | | | | | | | | | | |
| 001 | 06 | | HA | 2-0 | 24-51-61 | C00309 | A1 | N2 | | K00101 | A2 | F3 | | 050-099 | |
| 001 | 06 | | HA | 1-6 | 24-51-61 | C00309 | A1 | N2 | | K00101 | A2 | F3 | | 150-199, 275-299 | |
| 002 | 06 | | HA | 2-0 | 24-51-61 | C00309 | B1 | N2 | | K00101 | B2 | F3 | | 050-099 | |
| 002 | 06 | | HA | 1-6 | 24-51-61 | C00309 | B1 | N2 | | K00101 | B2 | F3 | | 150-199, 275-299 | |
| 003 | 06 | | HA | 2-0 | 24-51-61 | C00309 | C1 | N2 | | K00101 | C2 | F3 | | 050-099 | |
| 003 | 06 | | HA | 1-6 | 24-51-61 | C00309 | C1 | N2 | | K00101 | C2 | F3 | | 150-199, 275-299 | |
| 004 | 06 | | HA | 1-6 | 24-51-61 | C00309 | A1 | N2 | | C00351 | A2 | N2 | | ALL | |
| 005 | 06 | | HA | 1-6 | 24-51-61 | C00309 | B1 | N2 | | C00351 | B2 | N2 | | ALL | |
| 006 | 06 | | HA | 1-6 | 24-51-61 | C00309 | C1 | N2 | | C00351 | C2 | N2 | | ALL | |
| 007 | 06 | | HA | 1-0 | 24-51-61 | C00351 | A2 | N2 | | C00350 | A2 | N2 | | ALL | |
| 008 | 06 | | HA | 1-0 | 24-51-61 | C00351 | B2 | N2 | | C00350 | B2 | N2 | | ALL | |
| 009 | 06 | | HA | 1-0 | 24-51-61 | C00351 | C2 | N2 | | C00350 | C2 | N2 | | ALL | |
| W1011 | 286T1011 | SATCOM SYSTEM , E11,SHELF | | | | | | | | | | | | | |
| 001 | 20 | | PA | 2-0 | 23-25-11 | D06163J | | | 1 | D02653C | | | 8 | 156-157, 166-199, 277-299 | |
| 002 | 20 | | PA | 2-0 | 23-25-11 | D06163J | | | 2 | D02653C | | | 7 | 156-157, 166-199, 277-299 | |
| 003 | 20 | | PA | 2-0 | 23-25-11 | D06163J | | | 3 | D02653C | | | 1 | 156-157, 166-199, 277-299 | |
| 006 | 24 | | PK | 1-0 | 23-25-11 | D02653A | | A05 | | D02653A | | D05 | | 156-157, 166-199, 277-299 | |
| 202B | 24 | | PW | IB | 2-0 | 23-25-11 | D06163J | | 6 | D02653A | | B01 | | 156-157, 166-199, 277-299 | |
| 202R | 24 | | PW | IB | 0-0 | 23-25-11 | D06163J | | 5 | D02653A | | A01 | | 156-157, 166-199, 277-299 | |
| 202Z | | | | IB | 0-0 | 23-25-11 | D06163J | | 4 | D02653A | | DED | | 156-157, 166-199, 277-299 | |
| 203B | 24 | | PW | IC | 2-0 | 23-25-11 | D06163J | | 8 | D02653A | | D01 | | 156-157, 166-199, 277-299 | |
| 203R | 24 | | PW | IC | 0-0 | 23-25-11 | D06163J | | 7 | D02653A | | C01 | | 156-157, 166-199, 277-299 | |
| 203Z | | | | IC | 0-0 | 23-25-11 | D06163J | | 9 | D02653A | | DED | | 156-157, 166-199, 277-299 | |
| W1012 | 286T1012 | P34-N1-115VAC GND HNDLG BUS LOAD DISTRIBUTION | | | | | | | | | | | | | |
| 001 | 22 | | PA | 9-0 | 24-54-61 | T00103 | A | C | | C00304 | A2 | D | | ALL | |
| 002 | 22 | | PA | 9-0 | 24-54-61 | T00103 | B | C | | C00304 | B2 | D | | ALL | |
| 003 | 22 | | PA | 9-0 | 24-54-61 | T00103 | C | C | | C00304 | C2 | D | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1010

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1012 | 286T1012 | | | P34-N1-115VAC GND HNDLG BUS LOAD DISTRIBUTION (continued) | | | | | | | | | | | |
| 004 | 10 | PA | | 2-0 | 24-54-61 | T00103 | - | D | | GD03094 | D.. | E | | ALL | |
| 005 | 10 | PA | | 9-0 | 24-54-61 | T00103 | + | D | | C00746 | 2 | D | * | ALL | |
| 006 | 10 | PA | | 3-0 | 24-54-61 | C01040 | 2 | D | * | C00746 | 2 | D | * | ALL | |
| 007 | 10 | PA | | 2-0 | 24-54-61 | C01040 | 2 | D | * | C00707 | 2 | D | * | ALL | |
| 008 | 10 | PA | | 4-0 | 24-54-61 | C01354 | 1 | D | * | C01187 | 1 | D | | 050-099 | |
| 008 | 10 | PA | | 5-0 | 24-54-61 | C01354 | 1 | D | | C01187 | 1 | D | * | 275-276 | |
| 008 | 10 | PA | | 4-0 | 24-54-61 | C01354 | 1 | D | | C01187 | 1 | D | * | 277-299 | |
| 009 | 10 | PA | | 4-0 | 24-54-61 | C01354 | 1 | D | * | C00707 | 2 | D | * | 050-099 | |
| 009 | 10 | PA | | 5-0 | 24-54-61 | C01187 | 1 | D | * | C01354 | 1 | D | | 150-155 | |
| 009 | 10 | PA | | 4-0 | 24-54-61 | C00707 | 2 | D | * | C01354 | 1 | D | | 162-165 | |
| 010 | 10 | PA | | 5-0 | 24-54-61 | C01354 | 1 | D | | C01375 | 2 | D | * | 156-157, 166-199 | |
| 014 | 12 | HA | | 4-0 | 24-51-61 | C01154 | 1 | M | * | C01300 | 1 | M | | 050-099, 150-199 | |
| 015 | 20 | PA | | 2-0 | 24-54-61 | T00103 | N | C | | GD0002 | A.. | 2 | | ALL | |
| 016 | 12 | HA | | 3-0 | 24-51-61 | C00360 | A2 | M | * | C00304 | A1 | M | * | ALL | |
| 017 | 12 | HA | | 3-0 | 24-51-61 | C01167 | 1 | M | * | C00304 | A1 | M | * | 050-099 | |
| 017 | 12 | HA | | 3-0 | 24-51-61 | C01300 | 1 | M | | C00304 | A1 | M | * | 275-299 | |
| 019 | 12 | HA | | 4-0 | 24-51-61 | C00304 | A1 | M | * | C01154 | 1 | M | * | 150-199 | |
| 026 | 12 | HA | | 3-0 | 24-51-61 | C00304 | B1 | M | * | C01290 | 1 | M | | 150-199 | |
| 028 | 12 | HA | | 3-0 | 24-51-61 | C00304 | B1 | M | * | C01290 | 1 | M | | 050-099 | |
| 028 | 12 | HA | | 3-0 | 24-51-61 | C00304 | B1 | M | * | C01215 | 1 | M | | 275-299 | |
| 029 | 12 | HA | | 3-0 | 24-51-61 | C00304 | B1 | M | * | C00360 | B2 | M | * | ALL | |
| 030 | 12 | HA | | 3-0 | 24-51-61 | C00360 | C2 | M | * | C00304 | C1 | M | * | ALL | |
| 031 | 12 | HA | | 4-0 | 24-51-61 | C01209 | 1 | M | | C00304 | C1 | M | * | 050-099, 275-299 | |
| 033 | 12 | HA | | 4-0 | 24-51-61 | C01209 | 1 | M | | C00304 | C1 | M | * | 150-199 | |
| 038 | 12 | HA | | 9-0 | 24-51-61 | C00309 | A2 | M | | C00361 | A2 | M | * | ALL | |
| 039 | 12 | HA | | 9-0 | 24-51-61 | C00309 | B2 | M | | C00361 | B2 | M | * | ALL | |
| 040 | 12 | HA | | 9-0 | 24-51-61 | C00309 | C2 | M | | C00361 | C2 | M | * | ALL | |
| 041 | 12 | HA | | 2-0 | 24-51-61 | C00361 | C2 | M | * | C00360 | C2 | M | * | ALL | |
| 042 | 12 | HA | | 2-0 | 24-51-61 | C00361 | B2 | M | * | C00360 | B2 | M | * | ALL | |
| 043 | 12 | HA | | 2-0 | 24-51-61 | C00361 | A2 | M | * | C00360 | A2 | M | * | ALL | |
| 058 | 10 | PA | | 4-0 | 24-54-61 | C00707 | 2 | D | * | C01187 | 1 | D | * | 150-155 | |
| 058 | 10 | PA | | 4-0 | 24-54-61 | C00707 | 2 | D | | C01187 | 1 | D | | 156-199 | |
| 059 | 10 | PA | | 4-0 | 24-54-61 | C01187 | 1 | D | * | C01375 | 2 | D | * | 275-276 | |
| 059 | 10 | PA | | 2-0 | 24-54-61 | C01187 | 1 | D | * | C01375 | 2 | D | * | 277-299 | |
| 063 | 12 | HA | | 2-0 | 24-51-61 | C01167 | 1 | M | * | C01154 | 1 | M | * | 050-099 | |
| 063 | 12 | HA | | 2-0 | 24-51-61 | C01167 | 1 | M | | C01154 | 1 | M | | 150-199 | |
| 064 | 10 | PA | | 4-0 | 24-54-61 | C00707 | 2 | D | * | C01375 | 2 | D | * | 156-157, 166-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W1010

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|--------|-------|------|------|--------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1013 | 286T1013 | | | | COAX-SATCOM,LGA TO LNA/DIP | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-11 | D02995 | = C1 | | | D02679 | = C1 | | | | | 167-199 |
| 01CX | | JB | A | 2-0 | 23-25-11 | D02995 | = A1 | | | D02679 | = A1 | | | | | 167-199 |
| W1014 | 286T1014 | | | | P31-L1-L GEN GCB & BTB 115VAC DISTRIBUTION | | | | | | | | | | | |
| 001 | 04 | HA | | 2-0 | 24-21-11 | C00902 | T1 | R | *1 | C00901 | L1 | R | *1 | | | ALL |
| 002 | 04 | HA | | 2-0 | 24-21-11 | C00902 | T2 | R | *2 | C00901 | L2 | R | *2 | | | ALL |
| 003 | 04 | HA | | 2-0 | 24-21-11 | C00902 | T3 | R | *3 | C00901 | L3 | R | *3 | | | ALL |
| 004 | 04 | HA | | 4-0 | 24-21-11 | C00902 | T1 | R | *1 | C00310 | A1 | M | | | | ALL |
| 005 | 04 | HA | | 4-0 | 24-21-11 | C00902 | T2 | R | *2 | C00310 | B1 | M | | | | ALL |
| 006 | 04 | HA | | 4-0 | 24-21-11 | C00902 | T3 | R | *3 | C00310 | C1 | M | | | | ALL |
| 007 | 04 | HA | | 2-0 | 24-21-11 | M00897 | A1 | H | *1 | M01636 | A1 | H | *1 | | | 050-099 |
| 007 | 04 | HA | | 3-0 | 24-21-11 | M00897 | A1 | H | *1 | M01636 | A1 | H | *1 | | | 150-199 |
| 007 | 04 | HA | | 1-6 | 24-21-11 | M00897 | A1 | H | *1 | M00227 | A1 | H | *1 | | | 275-299 |
| 008 | 04 | HA | | 2-0 | 24-21-11 | M00897 | B1 | H | *2 | M01636 | B1 | H | *2 | | | 050-099 |
| 008 | 04 | HA | | 3-0 | 24-21-11 | M00897 | B1 | H | *2 | M01636 | B1 | H | *2 | | | 150-199 |
| 008 | 04 | HA | | 1-6 | 24-21-11 | M00897 | B1 | H | *2 | M00227 | B1 | H | *2 | | | 275-299 |
| 009 | 04 | HA | | 2-0 | 24-21-11 | M00897 | C1 | H | *3 | M01636 | C1 | H | *3 | | | 050-099 |
| 009 | 04 | HA | | 3-0 | 24-21-11 | M00897 | C1 | H | *3 | M01636 | C1 | H | *3 | | | 150-199 |
| 009 | 04 | HA | | 1-6 | 24-21-11 | M00897 | C1 | H | *3 | M00227 | C1 | H | *3 | | | 275-299 |
| 010 | 04 | HA | | 3-0 | 24-21-11 | M00897 | A1 | H | *1 | M00896 | A1 | H | *1 | | | 050-099 |
| 010 | 04 | HA | | 4-0 | 24-21-11 | M00897 | A1 | H | *1 | M00896 | A1 | H | *1 | | | 150-199 |
| 010 | 04 | HA | | 3-0 | 24-21-11 | M00897 | A1 | H | *1 | M00226 | A1 | H | *1 | | | 275-299 |
| 011 | 04 | HA | | 3-0 | 24-21-11 | M00897 | B1 | H | *2 | M00896 | B1 | H | *2 | | | 050-099 |
| 011 | 04 | HA | | 4-0 | 24-21-11 | M00897 | B1 | H | *2 | M00896 | B1 | H | *2 | | | 150-199 |
| 011 | 04 | HA | | 3-0 | 24-21-11 | M00897 | B1 | H | *2 | M00226 | B1 | H | *2 | | | 275-299 |
| 012 | 04 | HA | | 3-0 | 24-21-11 | M00897 | C1 | H | *3 | M00896 | C1 | H | *3 | | | 050-099 |
| 012 | 04 | HA | | 4-0 | 24-21-11 | M00897 | C1 | H | *3 | M00896 | C1 | H | *3 | | | 150-199 |
| 012 | 04 | HA | | 3-0 | 24-21-11 | M00897 | C1 | H | *3 | M00226 | C1 | H | *3 | | | 275-299 |
| 013 | 04 | HA | | 3-0 | 24-21-11 | C00311 | A1 | M | | M00896 | A1 | H | *1 | | | 050-099 |
| 013 | 04 | HA | | 3-6 | 24-21-11 | C00311 | A1 | M | | M00896 | A1 | H | *1 | | | 150-199, 275-299 |
| 014 | 04 | HA | | 3-0 | 24-21-11 | C00311 | B1 | M | | M00896 | B1 | H | *2 | | | 050-099 |
| 014 | 04 | HA | | 3-6 | 24-21-11 | C00311 | B1 | M | | M00896 | B1 | H | *2 | | | 150-199, 275-299 |
| 015 | 04 | HA | | 3-0 | 24-21-11 | C00311 | C1 | M | | M00896 | C1 | H | *3 | | | 050-099 |
| 015 | 04 | HA | | 5-0 | 24-21-11 | C00311 | C1 | M | | M00896 | C1 | H | *3 | | | 150-199, 275-299 |
| 016 | 04 | HA | | 1-0 | 24-21-11 | C00310 | A1 | M | | C00311 | A1 | M | | | | ALL |
| 017 | 04 | HA | | 1-0 | 24-21-11 | C00310 | B1 | M | | C00311 | B1 | M | | | | ALL |
| 018 | 04 | HA | | 1-0 | 24-21-11 | C00310 | C1 | M | | C00311 | C1 | M | | | | ALL |
| 019 | 04 | HA | | 2-0 | 24-21-11 | M00226 | A1 | H | *1 | M00896 | A1 | H | *1 | | | 275-299 |
| 020 | 04 | HA | | 2-0 | 24-21-11 | M00226 | B1 | H | *2 | M00896 | B1 | H | *2 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1010

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1014 | 286T1014 | | | P31-L1-L GEN GCB & BTB 115VAC DISTRIBUTION (continued) | | | | | | | | | | | | |
| 021 | 04 | | HA | 2-0 | 24-21-11 | M00226 | C1 | H | *3 | M00896 | C1 | H | *3 | 275-299 | | |
| 022 | 04 | | HA | 4-0 | 24-21-11 | C00902 | T1 | R | *4 | M01636 | A1 | H | *1 | 050-099 | | |
| 022 | 04 | | HA | 6-0 | 24-21-11 | C00902 | T1 | R | *4 | M01636 | A1 | H | *1 | 150-199 | | |
| 022 | 04 | | HA | 4-0 | 24-21-11 | C00902 | T1 | R | *4 | M00227 | A1 | H | *1 | 275-299 | | |
| 023 | 04 | | HA | 4-0 | 24-21-11 | C00902 | T2 | R | *5 | M01636 | B1 | H | *2 | 050-099 | | |
| 023 | 04 | | HA | 6-0 | 24-21-11 | C00902 | T2 | R | *5 | M01636 | B1 | H | *2 | 150-199 | | |
| 023 | 04 | | HA | 4-0 | 24-21-11 | C00902 | T2 | R | *5 | M00227 | B1 | H | *2 | 275-299 | | |
| 024 | 04 | | HA | 4-0 | 24-21-11 | C00902 | T3 | R | *6 | M01636 | C1 | H | *3 | 050-099 | | |
| 024 | 04 | | HA | 6-0 | 24-21-11 | C00902 | T3 | R | *6 | M01636 | C1 | H | *3 | 150-199 | | |
| 024 | 04 | | HA | 4-0 | 24-21-11 | C00902 | T3 | R | *6 | M00227 | C1 | H | *3 | 275-299 | | |
| 025 | 04 | | HA | 2-0 | 24-21-11 | C00902 | T1 | R | *4 | C00901 | L1 | R | *1 | ALL | | |
| 026 | 04 | | HA | 2-0 | 24-21-11 | C00902 | T2 | R | *5 | C00901 | L2 | R | *2 | ALL | | |
| 027 | 04 | | HA | 2-0 | 24-21-11 | C00902 | T3 | R | *6 | C00901 | L3 | R | *3 | ALL | | |
| W1016 | 286T1016 | | | P31-L1-L GEN 115VAC UTIL BUS PWR DISTRIBUTION | | | | | | | | | | | | |
| 001 | 08 | | PA | 5-0 | 24-51-13 | C00311 | A2 | D | | K00119 | A1 | E | | ALL | | |
| 002 | 08 | | PA | 5-0 | 24-51-13 | C00311 | B2 | D | | K00119 | B1 | E | | ALL | | |
| 003 | 08 | | PA | 5-0 | 24-51-13 | C00311 | C2 | D | | K00119 | C1 | E | | ALL | | |
| 004 | 08 | | PA | 5-0 | 24-51-12 | C00310 | A2 | D | | TB5032 | 1 | E | | ALL | | |
| 005 | 08 | | PA | 5-0 | 24-51-12 | C00310 | B2 | D | | TB5032 | 2 | E | | ALL | | |
| 006 | 08 | | PA | 5-0 | 24-51-12 | C00310 | C2 | D | | TB5032 | 3 | E | | ALL | | |
| 012 | 18 | | PA | 10-0 | 24-21-11 | C00901 | T3 | H | | L00128 | 1 | C | | ALL | | |
| 013 | 18 | | PA | 5-0 | 24-21-11 | C00901 | T1 | H | | TB0028F | A009 | 2 | | ALL | | |
| 014 | 18 | | PA | 5-0 | 24-21-11 | C00901 | T2 | H | | TB0028F | C009 | 2 | | ALL | | |
| 015 | 18 | | PA | 5-0 | 24-21-11 | C00901 | T3 | H | | TB0028F | A010 | 2 | | ALL | | |
| 016 | 18 | | PA | 9-0 | 24-21-11 | C00902 | T3 | H | | L00127 | 1 | C | | ALL | | |
| 017 | 18 | | PA | 8-0 | 24-21-11 | L00128 | 2 | C | | GDX0002 | A.. | 2 | | ALL | | |
| 018 | 18 | | PA | 8-0 | 24-21-11 | L00127 | 2 | C | | GDX0002 | A.. | 2 | | ALL | | |
| 019 | 18 | | PA | 8-0 | 24-21-51 | C00902 | L3 | H | | L00122 | 1 | C | | ALL | | |
| 020 | 18 | | PA | 8-0 | 24-21-51 | L00122 | 2 | C | | GDX0002 | A.. | 2 | | ALL | | |
| W1018 | 286T1018 | | | P32-R1-R GEN GCB & BTB 115V AC DISTRIBUTION | | | | | | | | | | | | |
| 001 | 04 | | HA | 2-0 | 24-21-21 | C00904 | T1 | R | *1 | C00903 | L1 | R | *1 | ALL | | |
| 002 | 04 | | HA | 2-0 | 24-21-21 | C00904 | T2 | R | *2 | C00903 | L2 | R | *2 | ALL | | |
| 003 | 04 | | HA | 2-0 | 24-21-21 | C00904 | T3 | R | *3 | C00903 | L3 | R | *3 | ALL | | |
| 004 | 04 | | HA | 4-0 | 24-21-21 | C00904 | T1 | R | *1 | C00317 | A1 | M | | 050-099 | | |
| 004 | 04 | | HA | 4-6 | 24-21-21 | C00904 | T1 | R | *1 | C00317 | A1 | M | | 150-199, 275-299 | | |
| 005 | 04 | | HA | 4-0 | 24-21-21 | C00904 | T2 | R | *2 | C00317 | B1 | M | | 050-099 | | |
| 005 | 04 | | HA | 4-6 | 24-21-21 | C00904 | T2 | R | *2 | C00317 | B1 | M | | 150-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11
Section W1010
Page 4
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1018 | 286T1018 | | | P32-R1-R GEN GCB & BTB 115V AC DISTRIBUTION (continued) | | | | | | | | | | | | |
| 006 | 04 | HA | | 4-0 | 24-21-21 | C00904 | T3 | R | *6 | C00317 | C1 | M | | 050-099 | | |
| 006 | 04 | HA | | 4-6 | 24-21-21 | C00904 | T3 | R | *6 | C00317 | C1 | M | | 150-199 | | |
| 006 | 04 | HA | | 7-0 | 24-21-21 | C00904 | T3 | R | *3 | C00317 | C1 | M | | 275-299 | | |
| 007 | 04 | HA | | 4-0 | 24-21-21 | C00904 | T1 | R | *4 | M01618 | A1 | H | *1 | 050-099 | | |
| 007 | 04 | HA | | 5-0 | 24-21-21 | C00904 | T1 | R | *4 | M01618 | A1 | H | * | 150-199 | | |
| 007 | 04 | HA | | 5-0 | 24-21-21 | C00904 | T1 | R | *4 | M00225 | A1 | H | * | 275-299 | | |
| 008 | 04 | HA | | 4-0 | 24-21-21 | C00904 | T2 | R | *5 | M01618 | B1 | H | *2 | 050-099 | | |
| 008 | 04 | HA | | 5-0 | 24-21-21 | C00904 | T2 | R | *5 | M01618 | B1 | H | * | 150-199 | | |
| 008 | 04 | HA | | 5-0 | 24-21-21 | C00904 | T2 | R | *5 | M00225 | B1 | H | * | 275-299 | | |
| 009 | 04 | HA | | 4-0 | 24-21-21 | C00904 | T3 | R | *3 | M01618 | C1 | H | *3 | 050-099 | | |
| 009 | 04 | HA | | 5-0 | 24-21-21 | C00904 | T3 | R | *3 | M01618 | C1 | H | * | 150-199 | | |
| 009 | 04 | HA | | 5-0 | 24-21-21 | C00904 | T3 | R | *6 | M00225 | C1 | H | * | 275-299 | | |
| 010 | 04 | HA | | 2-0 | 24-21-21 | M01617 | A1 | H | *1 | M01618 | A1 | H | *1 | 050-099 | | |
| 010 | 04 | HA | | 3-0 | 24-21-21 | M01617 | A1 | H | * | M01618 | A1 | H | * | 150-199 | | |
| 011 | 04 | HA | | 2-0 | 24-21-21 | M01617 | B1 | H | *2 | M01618 | B1 | H | *2 | 050-099 | | |
| 011 | 04 | HA | | 3-0 | 24-21-21 | M01617 | B1 | H | * | M01618 | B1 | H | * | 150-199 | | |
| 012 | 04 | HA | | 2-0 | 24-21-21 | M01617 | C1 | H | *3 | M01618 | C1 | H | *3 | 050-099 | | |
| 012 | 04 | HA | | 3-0 | 24-21-21 | M01617 | C1 | H | * | M01618 | C1 | H | * | 150-199 | | |
| 013 | 04 | HA | | 2-0 | 24-21-21 | M01617 | A1 | H | *1 | M00895 | A1 | H | *1 | 050-099 | | |
| 013 | 04 | HA | | 3-0 | 24-21-21 | M01617 | A1 | H | * | M00895 | A1 | H | *1 | 150-199 | | |
| 013 | 04 | HA | | 2-6 | 24-21-21 | M00225 | A1 | H | * | M00895 | A1 | H | *1 | 275-299 | | |
| 014 | 04 | HA | | 2-0 | 24-21-21 | M01617 | B1 | H | *2 | M00895 | B1 | H | *2 | 050-099 | | |
| 014 | 04 | HA | | 3-0 | 24-21-21 | M01617 | B1 | H | * | M00895 | B1 | H | *2 | 150-199 | | |
| 014 | 04 | HA | | 2-6 | 24-21-21 | M00225 | B1 | H | * | M00895 | B1 | H | *2 | 275-299 | | |
| 015 | 04 | HA | | 2-0 | 24-21-21 | M01617 | C1 | H | *3 | M00895 | C1 | H | *3 | 050-099 | | |
| 015 | 04 | HA | | 3-0 | 24-21-21 | M01617 | C1 | H | * | M00895 | C1 | H | *3 | 150-199 | | |
| 015 | 04 | HA | | 2-6 | 24-21-21 | M00225 | C1 | H | * | M00895 | C1 | H | *3 | 275-299 | | |
| 016 | 04 | HA | | 1-6 | 24-21-21 | M00898 | A1 | H | * | M00895 | A1 | H | *1 | ALL | | |
| 017 | 04 | HA | | 1-6 | 24-21-21 | M00898 | B1 | H | * | M00895 | B1 | H | *2 | ALL | | |
| 018 | 04 | HA | | 1-6 | 24-21-21 | M00898 | C1 | H | * | M00895 | C1 | H | *3 | ALL | | |
| 019 | 04 | HA | | 3-0 | 24-21-21 | M00898 | A1 | H | * | C00315 | A1 | M | | 050-099 | | |
| 019 | 04 | HA | | 3-6 | 24-21-21 | M00898 | A1 | H | * | C00315 | A1 | M | | 150-199 | | |
| 019 | 04 | HA | | 1-0 | 24-21-21 | C00303 | A1 | M | | C00315 | A1 | M | | 275-299 | | |
| 020 | 04 | HA | | 3-0 | 24-21-21 | M00898 | B1 | H | * | C00315 | B1 | M | | 050-099 | | |
| 020 | 04 | HA | | 3-6 | 24-21-21 | M00898 | B1 | H | * | C00315 | B1 | M | | 150-199 | | |
| 020 | 04 | HA | | 1-0 | 24-21-21 | C00303 | B1 | M | | C00315 | B1 | M | | 275-299 | | |
| 021 | 04 | HA | | 3-0 | 24-21-21 | M00898 | C1 | H | * | C00315 | C1 | M | | 050-099 | | |
| 021 | 04 | HA | | 3-6 | 24-21-21 | M00898 | C1 | H | * | C00315 | C1 | M | | 150-199 | | |
| 021 | 04 | HA | | 1-0 | 24-21-21 | C00303 | C1 | M | | C00315 | C1 | M | | 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W1010

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1018 | 286T1018 | | | P32-R1-R GEN GCB & BTB 115V AC DISTRIBUTION (continued) | | | | | | | | | | | |
| 022 | 04 | | HA | | 1-0 | 24-21-21 | C00316 | A1 | M | | C00315 | A1 | M | | ALL |
| 023 | 04 | | HA | | 1-0 | 24-21-21 | C00316 | B1 | M | | C00315 | B1 | M | | ALL |
| 024 | 04 | | HA | | 1-0 | 24-21-21 | C00316 | C1 | M | | C00315 | C1 | M | | ALL |
| 025 | 04 | | HA | | 1-0 | 24-21-21 | C00316 | A1 | M | | C00317 | A1 | M | | ALL |
| 026 | 04 | | HA | | 1-0 | 24-21-21 | C00316 | B1 | M | | C00317 | B1 | M | | ALL |
| 027 | 04 | | HA | | 1-0 | 24-21-21 | C00316 | C1 | M | | C00317 | C1 | M | | ALL |
| 028 | 04 | | HA | | 2-0 | 24-21-21 | C00903 | L1 | R | *1 | C00904 | T1 | R | *4 | ALL |
| 029 | 04 | | HA | | 2-0 | 24-21-21 | C00903 | L2 | R | *2 | C00904 | T2 | R | *5 | ALL |
| 030 | 04 | | HA | | 2-0 | 24-21-21 | C00903 | L3 | R | *3 | C00904 | T3 | R | *6 | ALL |
| 031 | 04 | | HA | | 4-0 | 24-21-21 | M00898 | A1 | H | * | C00303 | A1 | M | | 275-299 |
| 032 | 04 | | HA | | 4-0 | 24-21-21 | M00898 | B1 | H | * | C00303 | B1 | M | | 275-299 |
| 033 | 04 | | HA | | 4-0 | 24-21-21 | M00898 | C1 | H | * | C00303 | C1 | M | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1010
Page 6 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|----------|-------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1020 | 286T1020 | | | P32-R1-R GEN/115V AC UTIL & GND SVCE PWR DISTRIBUTION | | | | | | | | | | | |
| 001 | 08 | PA | | 3-8 | 24-51-52 | | K00102 | A3 | F | | C00316 | A2 | D | | ALL |
| 002 | 08 | PA | | 3-8 | 24-51-52 | | K00102 | B3 | F | | C00316 | B2 | D | | ALL |
| 003 | 08 | PA | | 3-8 | 24-51-52 | | K00102 | C3 | F | | C00316 | C2 | D | | ALL |
| 004 | 08 | PA | | 3-11 | 24-51-22 | | TB5034 | 4 | E | | C00317 | A2 | D | | ALL |
| 005 | 08 | PA | | 3-11 | 24-51-22 | | TB5034 | 5 | E | | C00317 | B2 | D | | ALL |
| 006 | 08 | PA | | 3-10 | 24-51-22 | | TB5034 | 6 | E | | C00317 | C2 | D | | ALL |
| 007 | 08 | PA | | 3-7 | 24-51-23 | | K00120 | A1 | E | | C00315 | A2 | D | | ALL |
| 008 | 08 | PA | | 3-5 | 24-51-23 | | K00120 | B1 | E | | C00315 | B2 | D | | ALL |
| 009 | 08 | PA | | 3-3 | 24-51-23 | | K00120 | C1 | E | | C00315 | C2 | D | | ALL |
| 010 | 18 | PA | | 8-9 | 24-21-21 | | C00904 | T3 | H | | L00125 | 1 | C | | ALL |
| 011 | 18 | PA | | 8-4 | 24-21-21 | | L00125 | 2 | C | | GDY0002 | A.. | 2 | | ALL |
| 012 | 18 | PA | | 10-5 | 24-28-11 | | C00819 | 1 | D | | C00903 | T2 | H | | ALL |
| 013 | 18 | PA | | 10-5 | 24-21-21 | | C00903 | T3 | H | | L00126 | 1 | C | | ALL |
| 014 | 18 | PA | | 8-3 | 24-21-21 | | L00126 | 2 | C | | GDY0002 | A.. | 2 | | ALL |
| 015 | 18 | PA | | 8-6 | 24-21-51 | | C00904 | L3 | H | | L00123 | 1 | C | | ALL |
| 016 | 18 | PA | | 8-4 | 24-21-51 | | L00123 | 2 | C | | GDY0002 | A.. | 2 | | ALL |
| 017 | 08 | PA | | 4-9 | 24-32-41 | | C00303 | A2 | D | | TB5034 | 1 | E | | 275-299 |
| 018 | 08 | PA | | 4-7 | 24-32-41 | | C00303 | B2 | D | | TB5034 | 2 | E | | 275-299 |
| 019 | 08 | PA | | 4-6 | 24-32-41 | | C00303 | C2 | D | | TB5034 | 3 | E | | 275-299 |
| W1024 | 286T1024 | | | P6-L1-115VAC PWR DISTRIBUTION | | | | | | | | | | | |
| 001 | 08 | PA | | 4-0 | 24-51-11 | | TB5002 | 1 | F | | C00308 | A1 | LA | * | ALL |
| 002 | 08 | PA | | 4-0 | 24-51-11 | | TB5002 | 2 | F | | C00308 | B1 | LA | * | ALL |
| 003 | 08 | PA | | 4-0 | 24-51-11 | | TB5002 | 3 | F | | C00308 | C1 | LA | * | ALL |
| 004 | 08 | PA | | 4-0 | 24-51-11 | | TB5002 | 1 | F | | C00328 | A1 | D | | ALL |
| 005 | 08 | PA | | 4-0 | 24-51-11 | | TB5002 | 2 | F | | C00328 | B1 | D | | ALL |
| 006 | 08 | PA | | 4-0 | 24-51-11 | | TB5002 | 3 | F | | C00328 | C1 | D | | ALL |
| 007 | 08 | PA | | 1-0 | 24-51-11 | | C00312 | A2 | LA | * | C00308 | A1 | LA | * | 050-099 |
| 007 | 08 | PA | | 1-0 | 24-51-11 | | C00312 | A2 | D | * | C00308 | A1 | LA | * | 150-199, 275-299 |
| 008 | 08 | PA | | 1-0 | 24-51-11 | | C00312 | B2 | LA | * | C00308 | B1 | LA | * | 050-099 |
| 008 | 08 | PA | | 1-0 | 24-51-11 | | C00312 | B2 | D | * | C00308 | B1 | LA | * | 150-199, 275-299 |
| 009 | 08 | PA | | 1-0 | 24-51-11 | | C00312 | C2 | LA | * | C00308 | C1 | LA | * | 050-099 |
| 009 | 08 | PA | | 1-0 | 24-51-11 | | C00312 | C2 | D | * | C00308 | C1 | LA | * | 150-199, 275-299 |
| 010 | 08 | PA | | 1-0 | 24-51-11 | | C00313 | A2 | D | | C00312 | A2 | LA | * | 050-099 |
| 010 | 12 | PA | | 1-0 | 24-51-11 | | C00313 | A2 | D | | C00312 | A2 | D | * | 150-199, 275-299 |
| 011 | 08 | PA | | 1-0 | 24-51-11 | | C00313 | B2 | D | | C00312 | B2 | LA | * | 050-099 |
| 011 | 12 | PA | | 1-0 | 24-51-11 | | C00313 | B2 | D | | C00312 | B2 | D | * | 150-199, 275-299 |
| 012 | 08 | PA | | 1-0 | 24-51-11 | | C00313 | C2 | D | | C00312 | C2 | LA | * | 050-099 |
| 012 | 12 | PA | | 1-0 | 24-51-11 | | C00313 | C2 | D | | C00312 | C2 | D | * | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1020

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1024 | 286T1024 | | | P6-L1-115VAC PWR DISTRIBUTION (continued) | | | | | | | | | | | |
| 013 | 08 | | PA | | 7-0 | 24-51-11 | C00328 | A2 | D | | C01138 | 2 | LA | * | ALL |
| 014 | 08 | | PA | | 7-0 | 24-51-11 | C00328 | B2 | D | | C00354 | B1 | LA | * | ALL |
| 015 | 08 | | PA | | 7-0 | 24-51-11 | C00328 | C2 | D | | C00354 | C1 | LA | * | ALL |
| 020 | 08 | | PA | | 2-0 | 24-51-11 | C01138 | 2 | LA | * | C00354 | A1 | LA | * | ALL |
| 022 | 08 | | PA | | 3-0 | 24-51-11 | C00354 | A1 | LA | * | C00331 | A1 | LA | * | ALL |
| 023 | 08 | | PA | | 1-0 | 24-51-11 | C00354 | B1 | LA | * | C00331 | B1 | LA | * | ALL |
| 025 | 08 | | PA | | 1-0 | 24-51-11 | C00354 | C1 | LA | * | C00331 | C1 | LA | * | ALL |
| 026 | 08 | | PA | | 2-0 | 24-51-11 | C00331 | A1 | LA | * | C00369 | A1 | LA | * | 050-099 |
| 026 | 08 | | PA | | 3-0 | 24-51-11 | C00331 | A1 | LA | * | C00369 | A1 | LA | * | 150-199, 275-299 |
| 027 | 08 | | PA | | 3-0 | 24-51-11 | C00331 | B1 | LA | * | C00369 | B1 | LA | * | ALL |
| 028 | 08 | | PA | | 3-0 | 24-51-11 | C00331 | C1 | LA | * | C00369 | C1 | LA | * | ALL |
| 029 | 08 | | PA | | 1-0 | 24-51-11 | C00369 | A1 | LA | * | C00368 | A2 | LA | * | ALL |
| 030 | 08 | | PA | | 1-0 | 24-51-11 | C00369 | B1 | LA | * | C00368 | B2 | LA | * | ALL |
| 031 | 08 | | PA | | 1-0 | 24-51-11 | C00369 | C1 | LA | * | C00368 | C2 | LA | * | ALL |
| 032 | 08 | | PA | | 2-0 | 24-51-11 | C00368 | A2 | LA | * | C00366 | A2 | D | | ALL |
| 033 | 08 | | PA | | 1-0 | 24-51-11 | C00368 | B2 | LA | * | C00366 | B2 | LA | * | ALL |
| 034 | 08 | | PA | | 1-0 | 24-51-11 | C00368 | C2 | LA | * | C00366 | C2 | D | | ALL |
| 036 | 08 | | PA | | 2-0 | 24-51-11 | C00366 | B2 | LA | * | C00876 | 2 | D | | ALL |
| 063 | 14 | | PA | | 5-0 | 24-51-11 | C00326 | C1 | D | | TB5002 | 3 | F | | ALL |
| 064 | 14 | | PA | | 5-0 | 24-51-11 | C00326 | B1 | D | | TB5002 | 2 | F | | ALL |
| 065 | 14 | | PA | | 5-0 | 24-51-11 | C00326 | A1 | D | | TB5002 | 1 | F | | ALL |
| W1026 | 286T1026 | | | P6-L1-L GEN PWR DISTRIBUTION | | | | | | | | | | | |
| 001 | 14 | | PA | | 6-0 | 24-32-11 | D04116J | 1 | | | C00312 | A1 | D | | ALL |
| 002 | 14 | | PA | | 6-0 | 24-32-11 | D04116J | 2 | | | C00312 | B1 | D | | ALL |
| 003 | 14 | | PA | | 6-0 | 24-32-11 | D04116J | 3 | | | C00312 | C1 | D | | ALL |
| 004 | 12 | | PA | | 6-0 | 24-51-11 | D04086J | 1 | | | C00313 | A1 | D | | ALL |
| 005 | 12 | | PA | | 6-0 | 24-51-11 | D04086J | 2 | | | C00313 | B1 | D | | ALL |
| 006 | 12 | | PA | | 6-0 | 24-51-11 | D04086J | 3 | | | C00313 | C1 | D | | ALL |
| 007 | 16 | | PA | | 6-0 | 24-51-11 | D04086J | 4 | | | C00308 | A2 | D | | ALL |
| 008 | 16 | | PA | | 6-0 | 24-51-11 | D04086J | 5 | | | C00308 | B2 | D | | ALL |
| 009 | 16 | | PA | | 6-0 | 24-51-11 | D04086J | 6 | | | C00308 | C2 | D | | ALL |
| 010 | 10 | | PA | | 3-0 | 24-53-11 | D04088J | B | | | T00123 | LV | E | | ALL |
| 011 | 16 | | PQ | A | 5-0 | 24-53-11 | C00877 | 1 | D | | T00123 | HV | E | | ALL |
| 011Z | | | | A | 0-0 | 24-53-11 | C00877 | DED | | | T00123 | DED | | | ALL |
| 012 | 16 | | PA | | 4-0 | 24-53-11 | GD02416 | A.. | 2 | | T00123 | GND | E | * | ALL |
| 013 | 18 | | PA | | 6-0 | 24-51-31 | C00884 | 1 | D | | TB0016F | A001 | 2 | | ALL |
| 014 | 22 | | PA | | 5-0 | 24-51-31 | C00876 | 1 | D | | TB0016Y | A002 | BJ | | ALL |
| 015 | 08 | | PA | | 5-0 | 24-54-11 | C00882 | 1 | D | | D04088J | A | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W1020
 Page 2
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|--|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1026 | 286T1026 | | | P6-L1-L GEN PWR DISTRIBUTION (continued) | | | | | | | | | | | | | | |
| 016 | 10 | PA | | 5-0 | 24-54-11 | C00883 | | 1 | D | * | | | | | | | | 050-099, 275-299 |
| 016 | 10 | PA | | 5-0 | 24-54-11 | C00883 | | 1 | D | | | | | | | | | 150-199 |
| 017 | 08 | PA | | 5-0 | 24-33-11 | C00886 | | 1 | LA | * | | | | | | | | ALL |
| 018 | 08 | PA | | 5-0 | 24-33-11 | C00885 | | 1 | D | | | | | | | | | ALL |
| 019 | 06 | HA | | 5-0 | 24-32-11 | C00881 | | 1 | F | | | | | | | | | ALL |
| 020 | 08 | PA | | 1-0 | 24-33-11 | C00886 | | 1 | LA | * | | | | | | | | ALL |
| 024 | 12 | PA | | 7-0 | 24-51-11 | C00313 | | | A1 | D | | | | | | | | ALL |
| 025 | 12 | PA | | 7-0 | 24-51-11 | C00313 | | | B1 | D | | | | | | | | ALL |
| 026 | 12 | PA | | 7-0 | 24-51-11 | C00313 | | | C1 | D | | | | | | | | ALL |
| 032 | 14 | PA | | 4-0 | 24-33-11 | TB5012 | | | 1 | C | | | | | | | | ALL |
| 035 | 18 | PA | | 4-0 | 24-33-11 | TB5012 | | | 2 | C | | | | | | | | ALL |
| 036 | 24 | PK | | 6-0 | 24-34-11 | TB0016X | | | C008 | BJ | | | | | | | * | ALL |
| 037 | 24 | PK | | 6-0 | 24-32-11 | TB0016X | | | D008 | BJ | | | | | | | * | ALL |
| 038 | 24 | PK | | 6-0 | 24-33-11 | TB0016Y | | | C002 | BJ | | | | | | | | ALL |
| 039 | 24 | PK | | 3-0 | 22-11-32 | D00894 | | | 5 | | | | | | | | | ALL |
| 040 | 12 | PA | | 5-0 | 24-51-42 | D08128J | | | 16 | | | | | | | | | ALL |
| 041 | 20 | PA | | 4-0 | 24-51-42 | D08128J | | | 2 | | | | | | | | | ALL |
| 042 | 12 | PA | | 5-0 | 24-51-42 | D08128J | | | 20 | | | | | | | | | ALL |
| 043 | 20 | PA | | 4-0 | 24-51-42 | D08128J | | | 4 | | | | | | | | | ALL |
| 044 | 12 | PA | | 5-0 | 24-51-42 | D08128J | | | 24 | | | | | | | | | ALL |
| 045 | 20 | PA | | 4-0 | 24-51-42 | D08128J | | | 6 | | | | | | | | | ALL |
| 046 | 24 | PK | | 3-0 | 24-51-42 | D00894 | | | 3 | | | | | | | | | ALL |
| 047 | 20 | PA | | 3-0 | 24-51-42 | D00894 | | | 18 | | | | | | | | | ALL |
| 048 | 22 | PA | | 3-0 | 24-51-42 | D00894 | | | 10 | | | | | | | | | ALL |
| 049 | 20 | PA | | 3-0 | 24-51-42 | D00894 | | | 19 | | | | | | | | | ALL |
| 050 | 24 | PK | | 5-0 | 24-51-42 | D00894 | | | 14 | | | | | | | | | ALL |
| 051 | 20 | PA | | 3-0 | 24-51-42 | D00894 | | | 15 | | | | | | | | | ALL |
| 052 | 20 | PA | | 5-0 | 24-51-42 | D00894 | | | 17 | | | | | | | | | ALL |
| 053 | 20 | PA | | 5-0 | 24-51-42 | D00894 | | | 6 | | | | | | | | | ALL |
| 054 | 20 | PA | | 5-0 | 24-51-42 | D00894 | | | 16 | | | | | | | | | ALL |
| 055 | 20 | PA | | 3-0 | 24-51-42 | D00894 | | | 7 | | | | | | | | | ALL |
| 056 | 24 | PK | | 3-0 | 24-51-42 | D00894 | | | 1 | | | | | | | | | ALL |
| 057 | 12 | PA | | 5-0 | 24-51-14 | D08128J | | | 18 | | | | | | | | * | ALL |
| 059 | 24 | PK | | 5-0 | 24-51-43 | TB0014F | | | A016 | 2 | | | | | | | | ALL |
| 060 | 12 | PA | | 5-0 | 24-51-14 | D08128J | | | 14 | | | | | | | | * | ALL |
| 061 | 12 | PA | | 3-0 | 24-51-14 | C00874 | | | 2 | D | * | | | | | | * | ALL |
| 062 | 12 | PA | | 6-0 | 24-51-14 | D06444J | | | 2 | | | | | | | | * | ALL |
| 063 | 12 | PA | | 2-0 | 24-51-14 | C01111 | | | 1 | D | * | | | | | | * | ALL |
| 064 | 20 | PA | | 4-0 | 24-51-14 | T00193 | | | HV2 | E | | | | | | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1020

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|---------|------|--------|--------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1026 | 286T1026 | | | P6-L1-L GEN PWR DISTRIBUTION (continued) | | | | | | | | | | | |
| 064 | 20 | | PA | | 4-0 | 24-51-14 | C00843 | | 2 | D | | T00193 | HV2 | E | 150-199, 275-299 |
| 065 | 18 | | PA | | 3-0 | 24-51-14 | D08128J | | 8 | DK | | T00193 | LV | E | 050-099 |
| 065 | 18 | | PA | | 3-0 | 24-51-14 | T00193 | | | LV | E | D08128J | 8 | DK | 150-199, 275-299 |
| 066 | 16 | | PA | | 3-0 | 24-51-14 | T00193 | | | GND | E | GD04756 | A.. | 2 | ALL |
| 067 | 12 | | PA | | 6-0 | 24-51-14 | D06444J | | 3 | | | C01113 | 1 | D | * 050-099 |
| 067 | 12 | | PA | | 6-0 | 24-51-14 | C01113 | | 1 | D | * | D06444J | 3 | | 150-199, 275-299 |
| 068 | 12 | | PA | | 2-0 | 24-51-14 | C01133 | | 2 | D | * | C01113 | 1 | D | * 050-099 |
| 068 | 12 | | PA | | 2-0 | 24-51-14 | C01113 | | 1 | D | * | C01133 | 2 | D | * 150-199, 275-299 |
| 069 | 12 | | PA | | 2-0 | 24-51-14 | C01122 | | 2 | D | * | C00843 | 1 | D | * ALL |
| 070 | 12 | | PA | | 5-0 | 24-51-14 | D08128J | | 22 | | | C01133 | 2 | D | * 050-099 |
| 070 | 12 | | PA | | 5-0 | 24-51-14 | C01133 | | 2 | D | * | D08128J | 22 | | 150-199, 275-299 |
| 071 | 14 | | PA | | 9-0 | 24-51-14 | D06448J | | 3 | | | C00326 | C2 | D | ALL |
| 072 | 14 | | PA | | 9-0 | 24-51-14 | D06448J | | 2 | | | C00326 | B2 | D | ALL |
| 073 | 14 | | PA | | 9-0 | 24-51-14 | D06448J | | 1 | | | C00326 | A2 | D | ALL |
| 074 | 20 | | PA | | 6-0 | 24-51-42 | D06448J | | 6 | | | D00894 | 13 | | ALL |
| 075 | 20 | | PA | | 6-0 | 24-51-42 | D06448J | | 5 | | | D00894 | 4 | | ALL |
| 076 | 20 | | PA | | 6-0 | 24-51-42 | D06448J | | 4 | | | D00894 | 12 | | ALL |
| 077 | 12 | | PA | | 6-0 | 24-51-14 | C01110 | | 1 | D | * | D06444J | 1 | | ALL |
| 078 | 16 | | PA | | 4-0 | 24-53-11 | GD02416 | | A.. | 2 | | T00123 | GND | E | * ALL |
| 084 | 08 | | PA | | 5-0 | 24-54-11 | C00883 | | 1 | D | * | TB5010 | 5 | F | 050-099, 275-299 |
| 084 | 08 | | PA | | 5-0 | 24-54-11 | C00883 | | 1 | D | | TB5010 | 5 | F | 150-199 |
| 085 | 12 | | PA | | 9-5 | 24-54-73 | TB5012 | | 3 | C | | C01190 | 1 | D | ALL |
| W1028 | 286T1028 | | | P6-R1-115VAC PWR DISTRIBUTION | | | | | | | | | | | |
| 001 | 08 | | PA | | 5-6 | 24-51-21 | C00329 | | A2 | D | | C01141 | 1 | LA | * ALL |
| 002 | 08 | | PA | | 5-2 | 24-51-21 | C00329 | | B2 | D | | C01117 | 1 | LA | * ALL |
| 003 | 08 | | PA | | 5-6 | 24-51-21 | C00329 | | C2 | D | | C01115 | 1 | LA | * ALL |
| 008 | 08 | | PA | | 1-6 | 24-51-21 | C01117 | | 1 | LA | * | C00878 | 2 | LA | * ALL |
| 010 | 08 | | PA | | 2-9 | 24-51-21 | C00307 | | A1 | LA | * | TB5008 | 1 | E | ALL |
| 011 | 08 | | PA | | 2-11 | 24-51-21 | C00307 | | B1 | LA | * | TB5008 | 2 | E | ALL |
| 012 | 08 | | PA | | 3-0 | 24-51-21 | C00307 | | C1 | LA | * | TB5008 | 3 | E | ALL |
| 013 | 08 | | PA | | 0-11 | 24-51-21 | C00307 | | A1 | LA | * | C00329 | A1 | LA | * ALL |
| 014 | 08 | | PA | | 0-11 | 24-51-21 | C00307 | | B1 | LA | * | C00329 | B1 | LA | * ALL |
| 015 | 08 | | PA | | 0-11 | 24-51-21 | C00307 | | C1 | LA | * | C00329 | C1 | LA | * ALL |
| 016 | 08 | | PA | | 0-11 | 24-51-21 | C00329 | | A1 | LA | * | C00318 | A2 | LA | * ALL |
| 017 | 08 | | PA | | 0-11 | 24-51-21 | C00329 | | B1 | LA | * | C00318 | B2 | LA | * ALL |
| 018 | 08 | | PA | | 0-11 | 24-51-21 | C00329 | | C1 | LA | * | C00318 | C2 | LA | * ALL |
| 019 | 08 | | PA | | 1-5 | 24-51-21 | C01141 | | 1 | LA | * | C00335 | A1 | LA | * ALL |
| 020 | 08 | | PA | | 1-1 | 24-51-21 | C00878 | | 2 | LA | * | C00335 | B1 | LA | * ALL |

WIRE LIST

D280T132

91-21-11

Section W1020

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1028 | 286T1028 | | | P6-R1-115VAC PWR DISTRIBUTION (continued) | | | | | | | | | | | | |
| 021 | 08 | PA | | 1-3 | 24-51-21 | C01115 | 1 | LA | * | C00335 | C1 | LA | * | ALL | | |
| 022 | 08 | PA | | 0-11 | 24-51-21 | C00335 | A1 | LA | * | C00355 | A2 | LA | * | ALL | | |
| 023 | 08 | PA | | 0-11 | 24-51-21 | C00335 | B1 | LA | * | C00355 | B2 | LA | * | ALL | | |
| 024 | 08 | PA | | 0-11 | 24-51-21 | C00335 | C1 | LA | * | C00355 | C2 | LA | * | ALL | | |
| 025 | 08 | PA | | 1-3 | 24-51-21 | C00355 | A2 | LA | * | C00371 | A2 | LA | * | 050-099 | | |
| 026 | 08 | PA | | 1-3 | 24-51-21 | C00355 | B2 | LA | * | C00371 | B2 | LA | * | 050-099 | | |
| 027 | 08 | PA | | 1-5 | 24-51-21 | C00355 | C2 | LA | * | C00371 | C2 | LA | * | 050-099 | | |
| 028 | 08 | PA | | 1-1 | 24-51-21 | C00371 | A2 | LA | * | C00325 | A1 | LA | * | ALL | | |
| 029 | 08 | PA | | 1-0 | 24-51-21 | C00371 | B2 | LA | * | C00325 | B1 | LA | * | ALL | | |
| 030 | 08 | PA | | 1-0 | 24-51-21 | C00371 | C2 | LA | * | C00325 | C1 | LA | * | ALL | | |
| 031 | 08 | PA | | 1-0 | 24-51-21 | C00325 | A1 | LA | * | C00370 | A1 | LA | * | ALL | | |
| 032 | 08 | PA | | 1-0 | 24-51-21 | C00325 | B1 | LA | * | C00370 | B1 | LA | * | ALL | | |
| 033 | 08 | PA | | 1-0 | 24-51-21 | C00325 | C1 | LA | * | C00370 | C1 | LA | * | ALL | | |
| 034 | 08 | PA | | 1-2 | 24-51-21 | C00370 | A1 | LA | * | C00324 | A2 | LA | * | ALL | | |
| 035 | 08 | PA | | 1-3 | 24-51-21 | C00370 | B1 | LA | * | C00324 | B2 | LA | * | ALL | | |
| 036 | 08 | PA | | 1-4 | 24-51-21 | C00370 | C1 | LA | * | C00324 | C2 | LA | * | ALL | | |
| 037 | 08 | PA | | 1-0 | 24-51-21 | C00324 | A2 | LA | * | C00323 | A2 | D | | ALL | | |
| 038 | 08 | PA | | 1-0 | 24-51-21 | C00324 | B2 | LA | * | C00323 | B2 | D | | ALL | | |
| 039 | 08 | PA | | 1-0 | 24-51-21 | C00324 | C2 | LA | * | C00323 | C2 | D | | ALL | | |
| 044 | 08 | PA | | 0-11 | 24-51-21 | C00318 | A2 | LA | * | C00319 | A2 | D | | ALL | | |
| 045 | 08 | PA | | 0-11 | 24-51-21 | C00318 | B2 | LA | * | C00319 | B2 | D | | ALL | | |
| 046 | 08 | PA | | 0-11 | 24-51-21 | C00318 | C2 | LA | * | C00319 | C2 | D | | ALL | | |
| 047 | 08 | PA | | 1-3 | 24-51-21 | C00355 | A2 | LA | | C00371 | A2 | LA | * | 150-199, 275-299 | | |
| 048 | 08 | PA | | 1-3 | 24-51-21 | C00355 | B2 | LA | | C00371 | B2 | LA | * | 150-199, 275-299 | | |
| 049 | 08 | PA | | 1-5 | 24-51-21 | C00355 | C2 | LA | | C00371 | C2 | LA | * | 150-199, 275-299 | | |
| 051 | 14 | PA | | 6-8 | 24-51-21 | C00327 | C1 | D | | TB5008 | 3 | E | | 050-099, 153-199, 275-299 | | |
| 051 | 18 | PA | | 6-8 | 24-51-21 | C00327 | C1 | D | | TB5008 | 3 | E | | 150-152 | | |
| 052 | 14 | PA | | 6-6 | 24-51-21 | C00327 | B1 | D | | TB5008 | 2 | E | | 050-099, 153-199, 275-299 | | |
| 052 | 18 | PA | | 6-6 | 24-51-21 | C00327 | B1 | D | | TB5008 | 2 | E | | 150-152 | | |
| 053 | 14 | PA | | 6-5 | 24-51-21 | C00327 | A1 | D | | TB5008 | 1 | E | | 050-099, 153-199, 275-299 | | |
| 053 | 18 | PA | | 6-5 | 24-51-21 | C00327 | A1 | D | | TB5008 | 1 | E | | 150-152 | | |

WIRE LIST
D280T132

91-21-11
Section W1020
Page 5 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1030 | 286T1030 | | | P6-R1-R GEN PWR DISTRIBUTION | | | | | | | | | | | |
| 001 | 14 | | PA | | 6-0 | 24-32-11 | C00318 | A1 | D | | D04120J | 1 | | | ALL |
| 002 | 14 | | PA | | 6-0 | 24-32-11 | C00318 | B1 | D | | D04120J | 2 | | | ALL |
| 003 | 14 | | PA | | 6-0 | 24-32-11 | C00318 | C1 | D | | D04120J | 3 | | | ALL |
| 004 | 06 | | HA | | 3-0 | 24-32-11 | C00889 | 1 | F | | K00108 | A1 | F7 | | ALL |
| 005 | 12 | | PA | | 6-0 | 24-51-21 | C00319 | A1 | D | | D04090J | 2 | | | ALL |
| 006 | 12 | | PA | | 6-0 | 24-51-21 | C00319 | B1 | D | | D04090J | 3 | | | ALL |
| 007 | 12 | | PA | | 6-0 | 24-51-21 | C00319 | C1 | D | | D04090J | 4 | | | ALL |
| 008 | 16 | | PA | | 6-0 | 24-51-21 | C00307 | A2 | D | | D04090J | 5 | | | ALL |
| 009 | 16 | | PA | | 6-0 | 24-51-21 | C00307 | B2 | D | | D04090J | 6 | | | ALL |
| 010 | 16 | | PA | | 6-0 | 24-51-21 | C00307 | C2 | D | | D04090J | 7 | | | ALL |
| 011 | 10 | | PA | | 3-0 | 24-53-21 | T00124 | LV | E | | D04092J | C | | | ALL |
| 012 | 16 | | PA | | 5-0 | 24-53-21 | T00124 | HV | E | | C00878 | 1 | D | | ALL |
| 013 | 16 | | PA | | 4-0 | 24-53-21 | T00124 | GND | E | * | GD02416 | A.. | 2 | | ALL |
| 014 | 08 | | PA | | 5-0 | 24-54-21 | C00891 | 1 | LA | * | D04092J | A | | | ALL |
| 015 | 08 | | PA | | 5-0 | 24-54-21 | C00890 | 1 | D | | D04092J | B | | | ALL |
| 016 | 12 | | PA | | 3-0 | 24-51-52 | D05858J | 4 | | | D04090J | 1 | | | ALL |
| 017 | 14 | | PA | | 6-0 | 27-51-11 | D05858J | 1 | | | C00323 | A1 | D | | ALL |
| 018 | 14 | | PA | | 6-0 | 27-51-11 | D05858J | 2 | | | C00323 | B1 | D | | ALL |
| 019 | 14 | | PA | | 6-0 | 27-51-11 | D05858J | 3 | | | C00323 | C1 | D | | ALL |
| 020 | 18 | | PA | | 5-0 | 27-81-21 | D05868J | 1 | | | C00325 | A2 | D | | ALL |
| 021 | 18 | | PA | | 5-0 | 27-81-21 | D05868J | 2 | | | C00325 | B2 | D | | ALL |
| 022 | 18 | | PA | | 5-0 | 27-81-21 | D05868J | 3 | | | C00325 | C2 | D | | ALL |
| 023 | 20 | | PA | | 5-0 | 27-81-11 | D05868J | 4 | | | C00324 | A1 | D | | ALL |
| 024 | 20 | | PA | | 5-0 | 27-81-11 | D05868J | 5 | | | C00324 | B1 | D | | ALL |
| 025 | 20 | | PA | | 5-0 | 27-81-11 | D05868J | 6 | | | C00324 | C1 | D | | ALL |
| 026 | 12 | | PA | | 5-0 | 24-51-52 | D05858J | 5 | | | C00314 | A2 | D | * | ALL |
| 027 | 12 | | PA | | 5-0 | 24-51-52 | D05858J | 6 | | | C00314 | B2 | D | * | ALL |
| 028 | 12 | | PA | | 5-0 | 24-51-52 | D05858J | 7 | | | C00314 | C2 | D | * | ALL |
| 029 | 12 | | PA | | 3-0 | 24-51-52 | C00372 | A2 | D | | C00314 | A2 | D | * | ALL |
| 030 | 12 | | PA | | 3-0 | 24-51-52 | C00730 | 2 | D | * | C00314 | B2 | D | * | ALL |
| 031 | 12 | | PA | | 3-0 | 24-51-52 | C00372 | C2 | D | | C00314 | C2 | D | * | ALL |
| 032 | 18 | | PA | | 5-0 | 25-29-11 | D05868J | 7 | | | C00314 | A1 | D | | ALL |
| 033 | 18 | | PA | | 5-0 | 25-29-11 | D05868J | 8 | | | C00314 | B1 | D | | ALL |
| 040 | 22 | | PA | | 5-0 | 30-31-21 | D05868J | 9 | | | C01117 | 2 | D | | ALL |
| 041 | 22 | | PA | | 5-0 | 30-31-23 | D05868J | 10 | | | C01115 | 2 | D | | ALL |
| 045 | 24 | | PK | | 4-0 | 24-51-42 | TB0016X | A009 | BJ | | C00802 | 1 | D | | ALL |
| 046 | 24 | | PK | | 4-0 | 24-34-11 | TB0016X | B009 | BJ | | C00802 | 1 | D | * | ALL |
| 047 | 24 | | PK | | 4-0 | 24-32-11 | TB0016X | C009 | BJ | | C00802 | 1 | D | * | ALL |
| 048 | 12 | | PA | | 7-0 | 24-51-21 | C00319 | A1 | D | | C04267 | 2 | D | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1030

Page 1

Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1030 | 286T1030 | | | P6-R1-R GEN PWR DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 049 | 12 | | PA | | 7-0 | 24-51-21 | C00319 | | B1 | D | | | C04268 | 2 | D | | ALL |
| 050 | 12 | | PA | | 7-0 | 24-51-21 | C00319 | | C1 | D | | | C04269 | 2 | D | | ALL |
| 051 | 16 | | PA | | 4-0 | 24-53-21 | T00124 | | GND | E | * | | GD02416 | A.. | 2 | | ALL |
| 054 | 12 | | PA | | 3-0 | 24-51-52 | C00372 | | B2 | D | | | C00730 | 2 | D | * | ALL |
| 055 | 18 | | PA | | 5-0 | 25-29-11 | D05868J | | 11 | | | | C00730 | 1 | D | | ALL |
| 056 | 08 | | PA | | 4-0 | 24-54-21 | C00891 | | 1 | LA | * | | TB5010 | 4 | F | | 050-099 |
| 056 | 08 | | PA | | 5-0 | 24-54-21 | C00891 | | 1 | LA | * | | TB5010 | 4 | F | | 150-199, 275-299 |
| 057 | 06 | | PA | | 5-0 | 25-29-12 | C00839 | | 1 | D | | | TB5010 | 3 | F | | ALL |
| 062 | 08 | | PA | | 9-6 | 24-54-21 | TB5010 | | 4 | F | | | C01191 | 1 | D | | 050-099, 150-152, 162-199, 275-299 |
| 062 | 08 | | PA | | 6-0 | 24-54-21 | C00891 | | 1 | LA | * | | C01191 | 1 | D | | 153-157 |
| W1032 | 286T1032 | | | P6-L1-L GEN 28 VDC DISTRIBUTION | | | | | | | | | | | | | |
| 001 | 06 | | HA | | 2-11 | 24-32-11 | C00881 | | 2 | F | * | | TB5010 | 1 | F | | ALL |
| 002 | 06 | | HA | | 1-1 | 24-32-11 | C00881 | | 2 | F | * | | C00883 | 2 | D | | ALL |
| 003 | 06 | | HA | | 1-1 | 24-32-11 | C00881 | | 2 | F | * | | C00886 | 2 | D | | ALL |
| 004 | 06 | | HA | | 0-10 | 24-32-11 | C00882 | | 2 | D | | | C00884 | 2 | D | | ALL |
| 005 | 06 | | HA | | 0-10 | 24-32-11 | C00885 | | 2 | D | | | C00801 | 2 | D | | ALL |
| W1035 | 286T1035 | | | E8 SHELF-EICAS UPPER DU SWITCHING MODULE | | | | | | | | | | | | | |
| 001 | 24 | | PK | | 3-0 | 31-41-12 | D05055J | | 1 | | | | TB0239Y | C001 | BJ | | ALL |
| 002 | 24 | | PK | | 3-0 | 31-41-12 | D05055J | | 2 | | | | TB0239Y | C002 | BJ | | ALL |
| 004 | 24 | | PK | | 3-0 | 31-41-12 | D00883A | | B03 | | | | TB0239Y | C001 | BJ | | ALL |
| 005 | 24 | | PK | | 3-0 | 31-41-12 | D00883A | | C03 | | | | TB0239Y | C002 | BJ | | ALL |
| 007 | 24 | | PK | | 3-0 | 31-41-12 | D00881A | | B03 | | | | TB0239Y | C001 | BJ | | ALL |
| 008 | 24 | | PK | | 3-0 | 31-41-12 | D00881A | | C03 | | | | TB0239Y | C002 | BJ | | ALL |
| 010 | 24 | | PK | | 3-0 | 31-41-16 | TB0239Y | | C005 | BJ | | | D00883A | F08 | | | ALL |
| 012 | 24 | | PK | | 3-0 | 31-41-16 | TB0239Y | | C004 | BJ | | | D00883B | J15 | | | ALL |
| 013 | 24 | | PK | | 3-0 | 31-41-16 | TB0239Y | | C004 | BJ | | | D05055J | 8 | | | ALL |
| 014 | 24 | | PK | | 3-0 | 31-41-16 | TB0239Y | | C005 | BJ | | | D05055J | 7 | | | ALL |
| 016 | 24 | | PK | | 3-0 | 31-41-16 | D00881B | | J15 | | | | TB0239Y | C004 | BJ | | ALL |
| 017 | 24 | | PK | | 3-0 | 31-41-16 | TB0239Y | | C005 | BJ | | | D00881A | F08 | | | ALL |
| 019 | 24 | | PK | | 3-0 | 31-41-15 | D00881D | | E10 | | | | TB0239X | A011 | BJ | | ALL |
| 020 | 24 | | PK | | 3-0 | 31-41-15 | D00881D | | E04 | | | | TB0239X | A012 | BJ | | ALL |
| 021 | 24 | | PK | | 3-0 | 31-41-15 | D00881D | | E06 | | | | TB0239X | A013 | BJ | | ALL |
| 022 | 24 | | PK | | 3-0 | 31-41-15 | D00881D | | E11 | | | | TB0239X | A014 | BJ | | ALL |
| 023 | 24 | | PK | | 3-0 | 31-41-15 | D00881D | | E03 | | | | TB0239X | A015 | BJ | | ALL |
| 024 | 24 | | PK | | 4-0 | 31-41-15 | D00881B | | F11 | | | | TB0239X | A016 | BJ | | ALL |
| 025 | 24 | | PK | | 4-0 | 31-41-15 | D00881B | | F07 | | | | TB0239X | A017 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1030

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1035 | 286T1035 | | | E8 SHELF-EICAS UPPER DU SWITCHING MODULE (continued) | | | | | | | | | | | |
| 026 | 24 | | PK | | 4-0 | 31-41-15 | D00881B | F02 | | | TB0239X | A018 | BJ | | ALL |
| 027 | 24 | | PK | | 4-0 | 31-41-15 | D00881B | F10 | | | TB0239X | A019 | BJ | | ALL |
| 028 | 24 | | PK | | 4-0 | 31-41-15 | D00881B | F06 | | | TB0239X | A020 | BJ | | ALL |
| 029 | 24 | | PK | | 3-0 | 31-41-15 | D00881F | B07 | | | TB0239X | B011 | BJ | | ALL |
| 030 | 24 | | PK | | 3-0 | 31-41-15 | D00881F | D08 | | | TB0239X | B012 | BJ | | ALL |
| 031 | 24 | | PK | | 4-0 | 31-41-15 | D00881B | C09 | | | TB0239X | B013 | BJ | | ALL |
| 032 | 24 | | PK | | 4-0 | SPARE | D00881B | C06 | | | TB0239X | B014 | BJ | | ALL |
| 033 | 24 | | PK | | 4-0 | SPARE | D00881B | D03 | | | TB0239X | B015 | BJ | | ALL |
| 034 | 24 | | PK | | 4-0 | SPARE | D00881B | D11 | | | TB0239X | B016 | BJ | | ALL |
| 035 | 24 | | PK | | 4-0 | SPARE | D00881B | B06 | | | TB0239X | B017 | BJ | | ALL |
| 036 | 24 | | PK | | 4-0 | SPARE | D00881B | E13 | | | TB0239X | B018 | BJ | | ALL |
| 037 | 24 | | PK | | 4-0 | SPARE | D00881E | G01 | | | TB0239X | B019 | BJ | | ALL |
| 038 | 24 | | PK | | 4-0 | SPARE | D00881D | D08 | | | TB0239X | B020 | BJ | | ALL |
| 039 | 24 | | PK | | 3-0 | SPARE | D00881A | K01 | | | TB0239X | C011 | BJ | | ALL |
| 040 | 24 | | PK | | 3-0 | SPARE | D00881A | K09 | | | TB0239X | C012 | BJ | | ALL |
| 041 | 24 | | PK | | 4-0 | SPARE | D00881B | K09 | | | TB0239X | C013 | BJ | | ALL |
| 042 | 24 | | PK | | 4-0 | SPARE | D00881B | K06 | | | TB0239X | C014 | BJ | | ALL |
| 043 | 24 | | PK | | 4-0 | SPARE | D00881D | K12 | | | TB0239X | C015 | BJ | | ALL |
| 044 | 24 | | PK | | 4-0 | SPARE | D00881D | J12 | | | TB0239X | C016 | BJ | | ALL |
| 045 | 24 | | PK | | 4-0 | SPARE | D00881E | K01 | | | TB0239X | C017 | BJ | | ALL |
| 046 | 24 | | PK | | 4-0 | SPARE | D00881E | J08 | | | TB0239X | C018 | BJ | | ALL |
| 047 | 24 | | PK | | 4-0 | SPARE | D00881F | J05 | | | TB0239X | C019 | BJ | | ALL |
| 048 | 24 | | PK | | 4-0 | 31-41-15 | D00881F | H05 | | | TB0239X | C020 | BJ | | ALL |
| 049 | 24 | | PK | | 4-0 | 31-41-15 | D00881E | J04 | | | TB0239X | D011 | BJ | | ALL |
| 050 | 24 | | PK | | 4-0 | 31-41-15 | D00881E | J01 | | | TB0239X | D012 | BJ | | ALL |
| 051 | 22 | | PA | | 1-0 | 31-41-15 | TB0239Z | 38 | BJ | | TB0239Z | 10 | BJ | | ALL |
| 052 | 20 | | PA | | 3-0 | 31-41-15 | TB0239Z | 38 | BJ | | GD00083 | D.. | 2 | | 050-099, 150-154, 275-276 |
| 052 | 20 | | PA | | 3-0 | 31-41-15 | TB0239Z | 38 | BJ | | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 |
| 052 | 20 | | PA | | 4-0 | 31-41-15 | TB0239Z | 38 | BJ | | GD00083 | D.. | 2 | | 162-164 |
| 053 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | AO11 | BJ | | TB0239Z | 10 | BJ | | 151 |
| 053 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | AO11 | BJ | | TB0239Z | 10 | % | | 165, 167-199 |
| 053 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | AO11 | BJ | | TB0239Z | 10 | BJ | | 166 |
| 054 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | AO15 | BJ | | TB0239Z | 10 | BJ | | ALL |
| 055 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | AO16 | BJ | | TB0239Z | 10 | BJ | | 151, 166 |
| 055 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | AO16 | BJ | | TB0239Z | 10 | % | | 165, 167-199 |
| 056 | 22 | | PA | | 1-0 | 31-41-15 | TB0239X | B011 | BJ | | TB0239Z | 9 | BJ | | ALL |
| 060 | 24 | | PV | CJ | 3-0 | 31-41-17 | D00875 | 47 | | | TB0239Z | 34 | BJ | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1030
Page 3
Aug 15/2007

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|---|---------------|------------------------|---|
| Wire No. | GA CO TY | Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice Effectivity |
| W1035 | 286T1035 | E8 SHELF-EICAS UPPER DU SWITCHING MODULE (continued) | | | |
| 060Z | | CJ | 0-0 31-41-17 | D00875 DED | TB0239Z DED ALL |
| 061 | 24 PK | | 3-0 31-41-17 | D00875 48 | TB0239Z 35 BJ ALL |
| 062 | 22 PA | | 3-0 31-41-17 | D05055J 9 | TB0239Z 35 BJ ALL |
| 063 | 22 PA | | 3-0 31-41-17 | D05055J 10 | TB0239Z 36 BJ ALL |
| 064 | 24 PK | | 4-0 31-41-17 | D00883B D04 | TB0239Z 36 BJ ALL |
| 065 | 24 PK | | 4-0 31-41-17 | D00881A E09 | TB0239Z 36 BJ ALL |
| 066 | 22 PA | | 4-0 31-41-17 | GD00083 D.. 2 | D00875 57 050-099, 150-154, 162-164, 275-276 |
| 066 | 22 PA | | 4-0 31-41-17 | GDX0002 D.. 2 | D00875 57 155-157, 165-199, 277-299 |
| 067 | 24 PK | | 5-0 31-31-13 | TB0237X B008 BJ | TB0239Z 35 BJ ALL |
| 080 | 22 PA | | 1-0 31-41-15 | TB0239Z 9 BJ | TB0239Z 38 BJ ALL |
| 087 | 22 PA | | 2-0 31-41-15 | TB0239X A012 BJ | TB0239Z 10 BJ 050-099, 155-199, 275-299 |
| 087 | 22 PA | | 1-0 31-41-15 | TB0239X A012 BJ | TB0239Z 10 BJ 150-154 |
| 088 | 22 PA | | 2-0 31-41-15 | TB0239X A017 BJ | TB0239Z 10 BJ ALL |
| 090 | 22 PA | | 1-0 31-41-15 | TB0239Z 8 BJ | TB0239Z 38 BJ ALL |
| 091 | 22 PA | | 1-0 31-41-15 | TB0239Z 7 BJ | TB0239Z 38 BJ ALL |
| 095 | 22 PA | | 2-0 31-41-15 | TB0239X A014 BJ | TB0239Z 10 BJ ALL |
| 104 | 24 PK | | 4-0 SPARE | D00881F B04 | TB0239Z REF % ALL |
| 105 | 24 PK | | 4-0 SPARE | D00881D K09 | TB0239Z REF % ALL |
| 106 | 24 PK | | 4-0 SPARE | D00881D K07 | TB0239Z REF % 050-099 |
| 106 | 24 PK | | 3-0 SPARE | D00881D K07 | TB0239Z % 150-154 |
| 106 | 24 PK | | 4-0 SPARE | D00881D K07 | TB0239Z % 155-199 |
| 201B | 24 PW IA | | 4-0 31-41-12 | D05055J 5 | D00881E F08 ALL |
| 201R | 24 PW IA | | 0-0 31-41-12 | D05055J 4 | D00881E F07 ALL |
| 201Z | | IA | 0-0 31-41-12 | D05055J 6 | GD00091 S.. 2 050-099, 150-154, 162-164, 275-276 |
| 201Z | | IA | 0-0 31-41-12 | D05055J 6 | GDX0002 S.. 2 155-157, 165-199, 277-299 |
| 202W | 26 BW IB | | 4-0 31-41-21 | D00881A C13 | D00875 2 ALL |
| 202WN | 26 BW IB | | 0-0 31-41-21 | D00881A C12 | D00875 1 ALL |
| 202Z | | IB | 0-0 31-41-21 | GD00081 S.. 2 | D00875 IB 050-099, 150-154, 162-164, 275-276 |
| 202Z | | IB | 0-0 31-41-21 | GDX0002 S.. 2 | D00875 IB 155-157, 165-199, 277-299 |
| 203W | 26 BW IC | | 4-0 31-41-21 | D00881A A04 | D00875 8 ALL |
| 203WN | 26 BW IC | | 0-0 31-41-21 | D00881A B04 | D00875 7 ALL |

WIRE LIST

D280T132

91-21-11

Section W1030

Page 4

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|--------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1035 | 286T1035 | | | | E8 SHELF-EICAS UPPER DU SWITCHING MODULE (continued) | | | | | | | | | | |
| 203Z | | | | IC | 0-0 | 31-41-21 | GD00081 | S.. | 2 | | D00875 | | | IC | 050-099, 150-154, 162-164, 275-276 |
| 203Z | | | | IC | 0-0 | 31-41-21 | GDX0002 | S.. | 2 | | D00875 | | | IC | 155-157, 165-199, 277-299 |
| 204W | 26 | | BW | ID | 4-0 | 31-41-21 | D00881A | C15 | | | D00875 | 14 | | | ALL |
| 204WN | 26 | | BW | ID | 0-0 | 31-41-21 | D00881A | C14 | | | D00875 | 13 | | | ALL |
| 204Z | | | | ID | 0-0 | 31-41-21 | GD00081 | S.. | 2 | | D00875 | | | ID | 050-099, 150-154, 162-164, 275-276 |
| 204Z | | | | ID | 0-0 | 31-41-21 | GDX0002 | S.. | 2 | | D00875 | | | ID | 155-157, 165-199, 277-299 |
| 205W | 26 | | BW | IE | 4-0 | 31-41-21 | D00881A | A05 | | | D00875 | 20 | | | ALL |
| 205WN | 26 | | BW | IE | 0-0 | 31-41-21 | D00881A | B05 | | | D00875 | 19 | | | ALL |
| 205Z | | | | IE | 0-0 | 31-41-21 | GD00081 | S.. | 2 | | D00875 | | | IE | 050-099, 150-154, 162-164, 275-276 |
| 205Z | | | | IE | 0-0 | 31-41-21 | GDX0002 | S.. | 2 | | D00875 | | | IE | 155-157, 165-199, 277-299 |
| 206W | 26 | | BW | IF | 4-0 | 31-41-21 | D00883A | C13 | | | D00875 | 60 | | | ALL |
| 206WN | 26 | | BW | IF | 0-0 | 31-41-21 | D00883A | C12 | | | D00875 | 59 | | | ALL |
| 206Z | | | | IF | 0-0 | 31-41-21 | GD00159 | S.. | 2 | | D00875 | | | IB | 050-099, 150-154, 162-164, 275-276 |
| 206Z | | | | IF | 0-0 | 31-41-21 | GDX0001 | S.. | 2 | | D00875 | | | IB | 155-157, 165-199, 277-299 |
| 207W | 26 | | BW | IG | 4-0 | 31-41-21 | D00883A | A04 | | | D00875 | 66 | | | ALL |
| 207WN | 26 | | BW | IG | 0-0 | 31-41-21 | D00883A | B04 | | | D00875 | 65 | | | ALL |
| 207Z | | | | IG | 0-0 | 31-41-21 | GD00159 | S.. | 2 | | D00875 | | | IC | 050-099, 150-154, 162-164, 275-276 |
| 207Z | | | | IG | 0-0 | 31-41-21 | GDX0001 | S.. | 2 | | D00875 | | | IC | 155-157, 165-199, 277-299 |
| 208W | 26 | | BW | IH | 4-0 | 31-41-21 | D00883A | C15 | | | D00875 | 72 | | | ALL |
| 208WN | 26 | | BW | IH | 0-0 | 31-41-21 | D00883A | C14 | | | D00875 | 71 | | | ALL |
| 208Z | | | | IH | 0-0 | 31-41-21 | GD00159 | S.. | 2 | | D00875 | | | ID | 050-099, 150-154, 162-164, 275-276 |
| 208Z | | | | IH | 0-0 | 31-41-21 | GDX0001 | S.. | 2 | | D00875 | | | ID | 155-157, 165-199, 277-299 |
| 209W | 26 | | BW | II | 4-0 | 31-41-21 | D00883A | A05 | | | D00875 | 78 | | | ALL |
| 209WN | 26 | | BW | II | 0-0 | 31-41-21 | D00883A | B05 | | | D00875 | 77 | | | ALL |
| 209Z | | | | II | 0-0 | 31-41-21 | GD00159 | S.. | 2 | | D00875 | | | IE | 050-099, 150-154, 162-164, 275-276 |

WIRE LIST
D280T132

91-21-11
Section W1030
Page 5
Aug 15/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1035 | 286T1035 | | | | E8 SHELF-EICAS UPPER DU SWITCHING MODULE (continued) | | | | | | | | | | | | |
| 209Z | | | | II | 0-0 | 31-41-21 | GDX0001 | S.. | 2 | | | | D00875 | | | IE | 155-157, 165-199, 277-299 |
| 210W | 26 | BW | IJ | | 4-0 | 31-41-21 | D00875 | | 4 | | | | D05055J | 12 | | | ALL |
| 210WN | 26 | BW | IJ | | 0-0 | 31-41-21 | D00875 | | 3 | | | | D05055J | 11 | | | ALL |
| 210Z | | | | | 0-0 | 31-41-21 | D00875 | | | | | IB | D05055J | 13 | | | ALL |
| 211W | 26 | BW | IK | | 4-0 | 31-41-21 | D00875 | | 10 | | | | D05055J | 15 | | | ALL |
| 211WN | 26 | BW | IK | | 0-0 | 31-41-21 | D00875 | | 9 | | | | D05055J | 14 | | | ALL |
| 211Z | | | | | 0-0 | 31-41-21 | D00875 | | | | | IC | D05055J | 16 | | | ALL |
| 212W | 26 | BW | IL | | 4-0 | 31-41-21 | D00875 | | 16 | | | | D05055J | 18 | | | ALL |
| 212WN | 26 | BW | IL | | 0-0 | 31-41-21 | D00875 | | 15 | | | | D05055J | 17 | | | ALL |
| 212Z | | | | | 0-0 | 31-41-21 | D00875 | | | | | ID | D05055J | 19 | | | ALL |
| 213W | 26 | BW | IM | | 4-0 | 31-41-21 | D00875 | | 22 | | | | D05055J | 21 | | | ALL |
| 213WN | 26 | BW | IM | | 0-0 | 31-41-21 | D00875 | | 21 | | | | D05055J | 20 | | | ALL |
| 213Z | | | | | 0-0 | 31-41-21 | D00875 | | | | | IE | D05055J | 22 | | | ALL |
| 214W | 26 | BW | IN | | 4-0 | 31-41-22 | D00881A | | C11 | | | | D00875 | 44 | | | ALL |
| 214WN | 26 | BW | IN | | 0-0 | 31-41-22 | D00881A | | C10 | | | | D00875 | 43 | | | ALL |
| 214Z | | | | IN | 0-0 | 31-41-22 | GD00081 | S.. | 2 | | | | D00875 | | | IN | 050-099, 150-154, 162-164, 275-276 |
| 214Z | | | | IN | 0-0 | 31-41-22 | GDX0002 | S.. | 2 | | | | D00875 | | | IN | 155-157, 165-199, 277-299 |
| 215W | 26 | BW | IO | | 4-0 | 31-41-22 | D00881A | | C02 | | | | D00875 | 26 | | | ALL |
| 215WN | 26 | BW | IO | | 0-0 | 31-41-22 | D00881A | | C01 | | | | D00875 | 25 | | | ALL |
| 215Z | | | | | 0-0 | 31-41-22 | GD00081 | S.. | 2 | | | | D00875 | | | IO | 050-099, 150-154, 162-164, 275-276 |
| 215Z | | | | IO | 0-0 | 31-41-22 | GDX0002 | S.. | 2 | | | | D00875 | | | IO | 155-157, 165-199, 277-299 |
| 216W | 26 | BW | IP | | 4-0 | 31-41-22 | D00881B | | B01 | | | | D00875 | 32 | | | ALL |
| 216WN | 26 | BW | IP | | 0-0 | 31-41-22 | D00881B | | A01 | | | | D00875 | 31 | | | ALL |
| 216Z | | | | | 0-0 | 31-41-22 | GD00089 | S.. | 2 | | | | D00875 | | | IP | 050-099, 150-154, 162-164, 275-276 |
| 216Z | | | | IP | 0-0 | 31-41-22 | GDX0002 | S.. | 2 | | | | D00875 | | | IP | 155-157, 165-199, 277-299 |
| 217W | 26 | BW | IQ | | 4-0 | 31-41-22 | D00881B | | B02 | | | | D00875 | 38 | | | ALL |
| 217WN | 26 | BW | IQ | | 0-0 | 31-41-22 | D00881B | | A02 | | | | D00875 | 37 | | | ALL |
| 217Z | | | | | 0-0 | 31-41-22 | GD00089 | S.. | 2 | | | | D00875 | | | IQ | 050-099, 150-154, 162-164, 275-276 |
| 217Z | | | | IQ | 0-0 | 31-41-22 | GDX0002 | S.. | 2 | | | | D00875 | | | IQ | 155-157, 165-199, 277-299 |
| 218W | 26 | BW | IR | | 4-0 | 31-41-22 | D00883A | | C11 | | | | D00875 | 102 | | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|--------|--------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1035 | 286T1035 | | | | E8 SHELF-EICAS UPPER DU SWITCHING MODULE (continued) | | | | | | | | | | |
| 218WN | 26 | BW | IR | 0-0 | 31-41-22 | D00883A | C10 | | | | D00875 | 101 | | ALL | |
| 218Z | | | IR | 0-0 | 31-41-22 | GD00159 | S.. | 2 | | | D00875 | | IN | 050-099, 150-154, 162-164, 275-276 | |
| 218Z | | | IR | 0-0 | 31-41-22 | GDX0001 | S.. | 2 | | | D00875 | | IN | 155-157, 165-199, 277-299 | |
| 219W | 26 | BW | IS | 4-0 | 31-41-22 | D00883A | C02 | | | | D00875 | 84 | | ALL | |
| 219WN | 26 | BW | IS | 0-0 | 31-41-22 | D00883A | C01 | | | | D00875 | 83 | | ALL | |
| 219Z | | | IS | 0-0 | 31-41-22 | GD00159 | S.. | 2 | | | D00875 | | IO | 050-099, 150-154, 162-164, 275-276 | |
| 219Z | | | IS | 0-0 | 31-41-22 | GDX0001 | S.. | 2 | | | D00875 | | IO | 155-157, 165-199, 277-299 | |
| 220W | 26 | BW | IT | 4-0 | 31-41-22 | D00883B | B01 | | | | D00875 | 90 | | ALL | |
| 220WN | 26 | BW | IT | 0-0 | 31-41-22 | D00883B | A01 | | | | D00875 | 89 | | ALL | |
| 220Z | | | IT | 0-0 | 31-41-22 | GD00151 | S.. | 2 | | | D00875 | | IP | 050-099, 150-154, 162-164, 275-276 | |
| 220Z | | | IT | 0-0 | 31-41-22 | GDX0001 | S.. | 2 | | | D00875 | | IP | 155-157, 165-199, 277-299 | |
| 221W | 26 | BW | IU | 4-0 | 31-41-22 | D00883B | B02 | | | | D00875 | 96 | | ALL | |
| 221WN | 26 | BW | IU | 0-0 | 31-41-22 | D00883B | A02 | | | | D00875 | 95 | | ALL | |
| 221Z | | | IU | 0-0 | 31-41-22 | GD00151 | S.. | 2 | | | D00875 | | IQ | 050-099, 150-154, 162-164, 275-276 | |
| 221Z | | | IU | 0-0 | 31-41-22 | GDX0001 | S.. | 2 | | | D00875 | | IQ | 155-157, 165-199, 277-299 | |
| 222W | 26 | BW | IV | 4-0 | 31-41-22 | D05055J | | 24 | | | D00875 | 46 | | ALL | |
| 222WN | 26 | BW | IV | 0-0 | 31-41-22 | D05055J | | 23 | | | D00875 | 45 | | ALL | |
| 222Z | | | IV | 0-0 | 31-41-22 | D05055J | | 25 | | | D00875 | | IN | ALL | |
| 223W | 26 | BW | IW | 4-0 | 31-41-22 | D05055J | | 27 | | | D00875 | 28 | | ALL | |
| 223WN | 26 | BW | IW | 0-0 | 31-41-22 | D05055J | | 26 | | | D00875 | 27 | | ALL | |
| 223Z | | | IW | 0-0 | 31-41-22 | D05055J | | 28 | | | D00875 | | IO | ALL | |
| 224W | 26 | BW | IX | 4-0 | 31-41-22 | D05055J | | 30 | | | D00875 | 34 | | ALL | |
| 224WN | 26 | BW | IX | 0-0 | 31-41-22 | D05055J | | 29 | | | D00875 | 33 | | ALL | |
| 224Z | | | IX | 0-0 | 31-41-22 | D05055J | | 31 | | | D00875 | | IP | ALL | |
| 225W | 26 | BW | IY | 4-0 | 31-41-22 | D05055J | | 33 | | | D00875 | 40 | | ALL | |
| 225WN | 26 | BW | IY | 0-0 | 31-41-22 | D05055J | | 32 | | | D00875 | 39 | | ALL | |
| 225Z | | | IY | 0-0 | 31-41-22 | D05055J | | 34 | | | D00875 | | IQ | ALL | |
| W1036 | 286T1036 | | | | P6-R1-R GEN 28 VDC DISTRIBUTION | | | | | | | | | | |
| 001 | 06 | HA | | 3-0 | 24-32-11 | C00889 | | 2 | F | * | TB5010 | 2 | F | ALL | |
| 002 | 06 | HA | | 1-0 | 24-32-11 | C00889 | | 2 | F | * | C00890 | 2 | D | ALL | |

WIRE LIST

D280T132

91-21-11
Section W1030
Page 7
Aug 15/2007



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1036 | 286T1036 | | | P6-R1-R GEN 28 VDC DISTRIBUTION (continued) | | | | | | | | | | | | |
| 003 | 06 | | HA | 1-0 | 24-32-11 | C00891 | | 2 | D | | C00802 | 2 | D | | ALL | |
| 004 | 08 | | PA | 4-0 | 24-54-21 | TB5010 | | 4 | F | | C00839 | 2 | D | | ALL | |
| W1037 | 286T1037 | | | E8 SHELF-EICAS LOWER DU SWITCHING MODULE | | | | | | | | | | | | |
| 001 | 24 | | PK | 3-0 | 31-41-12 | D05057J | | 1 | | | TB0239Y | A001 | BJ | | ALL | |
| 002 | 24 | | PK | 3-0 | 31-41-12 | D05057J | | 2 | | | TB0239Y | A002 | BJ | | ALL | |
| 004 | 24 | | PK | 4-0 | 31-41-12 | D00883A | | | C04 | | TB0239Y | A001 | BJ | | ALL | |
| 005 | 24 | | PK | 4-0 | 31-41-12 | D00883A | | | C05 | | TB0239Y | A002 | BJ | | ALL | |
| 007 | 24 | | PK | 3-0 | 31-41-12 | D00881A | | | C04 | | TB0239Y | A001 | BJ | | ALL | |
| 008 | 24 | | PK | 3-0 | 31-41-12 | D00881A | | | C05 | | TB0239Y | A002 | BJ | | ALL | |
| 010 | 24 | | PK | 4-0 | 31-41-15 | D00883D | | | E10 | | TB0239X | A021 | BJ | | ALL | |
| 011 | 24 | | PK | 4-0 | 31-41-15 | D00883D | | | E04 | | TB0239X | A022 | BJ | | ALL | |
| 012 | 24 | | PK | 4-0 | 31-41-15 | D00883D | | | E06 | | TB0239X | A023 | BJ | | ALL | |
| 013 | 24 | | PK | 4-0 | 31-41-15 | D00883D | | | E11 | | TB0239X | A024 | BJ | | ALL | |
| 014 | 24 | | PK | 4-0 | 31-41-15 | D00883D | | | E03 | | TB0239X | A025 | BJ | | ALL | |
| 015 | 24 | | PK | 4-0 | 31-41-15 | D00883B | | | F11 | | TB0239X | A026 | BJ | | ALL | |
| 016 | 24 | | PK | 4-0 | 31-41-15 | D00883B | | | F07 | | TB0239X | A027 | BJ | | ALL | |
| 017 | 24 | | PK | 4-0 | 31-41-15 | D00883B | | | F02 | | TB0239X | A028 | BJ | | ALL | |
| 018 | 24 | | PK | 4-0 | 31-41-15 | D00883B | | | F10 | | TB0239X | A029 | BJ | | ALL | |
| 019 | 24 | | PK | 4-0 | 31-41-15 | D00883B | | | F06 | | TB0239X | A030 | BJ | | ALL | |
| 020 | 24 | | PK | 4-0 | 31-41-15 | D00883F | | | B07 | | TB0239X | B021 | BJ | | ALL | |
| 021 | 24 | | PK | 4-0 | 31-41-15 | D00883F | | | D08 | | TB0239X | B022 | BJ | | ALL | |
| 022 | 24 | | PK | 4-0 | 31-41-15 | D00883B | | | C09 | | TB0239X | B023 | BJ | | ALL | |
| 023 | 24 | | PK | 4-0 | SPARE | D00883B | | | C06 | | TB0239X | B024 | BJ | | ALL | |
| 024 | 24 | | PK | 4-0 | SPARE | D00883B | | | D03 | | TB0239X | B025 | BJ | | ALL | |
| 025 | 24 | | PK | 4-0 | SPARE | D00883B | | | D11 | | TB0239X | B026 | BJ | | ALL | |
| 026 | 24 | | PK | 4-0 | SPARE | D00883B | | | B06 | | TB0239X | B027 | BJ | | ALL | |
| 027 | 24 | | PK | 4-0 | SPARE | D00883B | | | E13 | | TB0239X | B028 | BJ | | ALL | |
| 028 | 24 | | PK | 4-0 | SPARE | D00883E | | | G01 | | TB0239X | B029 | BJ | | ALL | |
| 029 | 24 | | PK | 4-0 | SPARE | D00883D | | | D08 | | TB0239X | B030 | BJ | | ALL | |
| 030 | 24 | | PK | 4-0 | SPARE | D00883A | | | K01 | | TB0239X | C021 | BJ | | ALL | |
| 031 | 24 | | PK | 4-0 | SPARE | D00883A | | | K09 | | TB0239X | C022 | BJ | | ALL | |
| 032 | 24 | | PK | 4-0 | SPARE | D00883B | | | K09 | | TB0239X | C023 | BJ | | ALL | |
| 033 | 24 | | PK | 4-0 | SPARE | D00883B | | | K06 | | TB0239X | C024 | BJ | | ALL | |
| 034 | 24 | | PK | 4-0 | SPARE | D00883D | | | K12 | | TB0239X | C025 | BJ | | ALL | |
| 035 | 24 | | PK | 4-0 | SPARE | D00883D | | | J12 | | TB0239X | C026 | BJ | | ALL | |
| 036 | 24 | | PK | 4-0 | SPARE | D00883E | | | K01 | | TB0239X | C027 | BJ | | ALL | |
| 037 | 24 | | PK | 4-0 | SPARE | D00883E | | | J08 | | TB0239X | C028 | BJ | | ALL | |
| 038 | 24 | | PK | 4-0 | SPARE | D00883F | | | J05 | | TB0239X | C029 | BJ | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1030

Page 8

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1037 | 286T1037 | | | E8 SHELF-EICAS LOWER DU SWITCHING MODULE (continued) | | | | | | | | | | | | |
| 039 | 24 | | PK | | 4-0 | 31-41-15 | D00883F | H05 | | | | TB0239X | C030 | BJ | | ALL |
| 040 | 24 | | PK | | 4-0 | 31-41-15 | D00883E | J04 | | | | TB0239X | D021 | BJ | | ALL |
| 041 | 24 | | PK | | 4-0 | 31-41-15 | D00883E | J01 | | | | TB0239X | D022 | BJ | | ALL |
| 042 | 22 | | PA | | 2-0 | 31-41-15 | TB0239Z | 39 | BJ | | | TB0239Z | 32 | BJ | | ALL |
| 043 | 20 | | PA | | 4-0 | 31-41-15 | TB0239Z | 39 | BJ | | | GD00159 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 |
| 043 | 20 | | PA | | 4-0 | 31-41-15 | TB0239Z | 39 | BJ | | | GDX0001 | D.. | 2 | | 155-157, 165-199, 277-299 |
| 044 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | A021 | BJ | | | TB0239Z | 32 | BJ | | 151, 166 |
| 044 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | A021 | BJ | | | TB0239Z | 32 | % | | 165, 167-199 |
| 045 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | A026 | BJ | | | TB0239Z | 32 | BJ | | 151, 166 |
| 045 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | A026 | BJ | | | TB0239Z | 32 | % | | 165, 167-199 |
| 046 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | B021 | BJ | | | TB0239Z | 31 | BJ | | ALL |
| 050 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | D022 | BJ | | | TB0239Z | 37 | BJ | | 050-099, 150-199, 275-276, 280-299 |
| 050 | 22 | | PA | | 3-0 | 31-41-15 | TB0239X | D022 | BJ | | | TB0239Z | 37 | BJ | | 277-278 |
| 051 | 24 | | PK | | 3-0 | 31-41-17 | D00877 | 47 | | | | TB0239Z | 34 | BJ | | ALL |
| 052 | 24 | | PK | | 3-0 | 31-41-17 | D00877 | 48 | | | | TB0239Z | 35 | BJ | | ALL |
| 053 | 24 | | PK | | 3-0 | 31-41-17 | D00883A | E09 | | | | D00881B | D04 | | | ALL |
| 054 | 22 | | PA | | 4-0 | 31-41-17 | GD00083 | D.. | 2 | | | D00877 | 57 | | | 050-099, 150-154, 275-276 |
| 054 | 22 | | PA | | 4-0 | 31-41-17 | GDX0002 | D.. | 2 | | | D00877 | 57 | | | 155-199, 277-299 |
| 066 | 22 | | PA | | 2-0 | 31-41-15 | TB0239Z | 31 | BJ | | | TB0239Z | 39 | BJ | | ALL |
| 074 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | A022 | BJ | | | TB0239Z | 32 | BJ | | ALL |
| 075 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | A027 | BJ | | | TB0239Z | 32 | BJ | | ALL |
| 083 | 24 | | PK | | 4-0 | SPARE | D00883F | B04 | | | | TB0239Z | REF | % | | ALL |
| 084 | 24 | | PK | | 4-0 | SPARE | D00883D | K09 | | | | TB0239Z | REF | % | | ALL |
| 085 | 24 | | PK | | 4-0 | SPARE | D00883D | K07 | | | | TB0239Z | REF | % | | 050-099 |
| 085 | 24 | | PK | | 3-0 | SPARE | D00883D | K07 | | | | TB0239Z | | % | | 150-154 |
| 085 | 24 | | PK | | 4-0 | SPARE | D00883D | K07 | | | | TB0239Z | | % | | 155-199 |
| 090 | 22 | | PA | | 2-0 | 31-41-15 | TB0239Z | 33 | BJ | | | TB0239Z | 39 | BJ | | ALL |
| 091 | 22 | | PA | | 2-0 | 31-41-15 | TB0239Z | 37 | BJ | | | TB0239Z | 39 | BJ | | ALL |
| 099 | 22 | | PA | | 2-0 | 31-41-15 | TB0239X | A024 | BJ | | | TB0239Z | 32 | BJ | | ALL |
| 201B | 24 | | PW | IA | 4-0 | 31-41-12 | D05057J | 5 | | | | D00883E | F08 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 31-41-12 | D05057J | 4 | | | | D00883E | F07 | | | ALL |
| 201Z | | | | IA | 0-0 | 31-41-12 | D05057J | 6 | | | | GD00151 | S.. | 2 | | 050-099, 150-154, 275-276 |
| 201Z | | | | IA | 0-0 | 31-41-12 | D05057J | 6 | | | | GDX0001 | S.. | 2 | | 155-199, 277-299 |
| 202W | 26 | | BW | IB | 4-0 | 31-41-23 | D00881A | A12 | | | | D00877 | 2 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1030
Page 9
Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|--------|--------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1037 | 286T1037 | | | | E8 SHELF-EICAS LOWER DU SWITCHING MODULE (continued) | | | | | | | | | | |
| 202WN | 26 | BW | IB | 0-0 | 31-41-23 | D00881A | B12 | | | | D00877 | 1 | | ALL | |
| 202Z | | | IB | 0-0 | 31-41-23 | GD00081 | S.. | 2 | | | D00877 | | IB | 050-099, 150-154, 275-276 | |
| 202Z | | | IB | 0-0 | 31-41-23 | GDX0002 | S.. | 2 | | | D00877 | | IB | 155-199, 277-299 | |
| 203W | 26 | BW | IC | 4-0 | 31-41-23 | D00881A | A14 | | | | D00877 | 8 | | ALL | |
| 203WN | 26 | BW | IC | 0-0 | 31-41-23 | D00881A | B14 | | | | D00877 | 7 | | ALL | |
| 203Z | | | IC | 0-0 | 31-41-23 | GD00081 | S.. | 2 | | | D00877 | | IC | 050-099, 150-154, 275-276 | |
| 203Z | | | IC | 0-0 | 31-41-23 | GDX0002 | S.. | 2 | | | D00877 | | IC | 155-199, 277-299 | |
| 204W | 26 | BW | ID | 4-0 | 31-41-23 | D00881A | A13 | | | | D00877 | 14 | | ALL | |
| 204WN | 26 | BW | ID | 0-0 | 31-41-23 | D00881A | B13 | | | | D00877 | 13 | | ALL | |
| 204Z | | | ID | 0-0 | 31-41-23 | GD00081 | S.. | 2 | | | D00877 | | ID | 050-099, 150-154, 275-276 | |
| 204Z | | | ID | 0-0 | 31-41-23 | GDX0002 | S.. | 2 | | | D00877 | | ID | 155-199, 277-299 | |
| 205W | 26 | BW | IE | 4-0 | 31-41-23 | D00881A | A15 | | | | D00877 | 20 | | ALL | |
| 205WN | 26 | BW | IE | 0-0 | 31-41-23 | D00881A | B15 | | | | D00877 | 19 | | ALL | |
| 205Z | | | IE | 0-0 | 31-41-23 | GD00081 | S.. | 2 | | | D00877 | | IE | 050-099, 150-154, 275-276 | |
| 205Z | | | IE | 0-0 | 31-41-23 | GDX0002 | S.. | 2 | | | D00877 | | IE | 155-199, 277-299 | |
| 206W | 26 | BW | IF | 4-0 | 31-41-23 | D00883A | A12 | | | | D00877 | 60 | | ALL | |
| 206WN | 26 | BW | IF | 0-0 | 31-41-23 | D00883A | B12 | | | | D00877 | 59 | | ALL | |
| 206Z | | | IF | 0-0 | 31-41-23 | GD00159 | S.. | 2 | | | D00877 | | IB | 050-099, 150-154, 275-276 | |
| 206Z | | | IF | 0-0 | 31-41-23 | GDX0001 | S.. | 2 | | | D00877 | | IB | 155-199, 277-299 | |
| 207W | 26 | BW | IG | 4-0 | 31-41-23 | D00883A | A14 | | | | D00877 | 66 | | ALL | |
| 207WN | 26 | BW | IG | 0-0 | 31-41-23 | D00883A | B14 | | | | D00877 | 65 | | ALL | |
| 207Z | | | IG | 0-0 | 31-41-23 | GD00159 | S.. | 2 | | | D00877 | | IC | 050-099, 150-154, 275-276 | |
| 207Z | | | IG | 0-0 | 31-41-23 | GDX0001 | S.. | 2 | | | D00877 | | IC | 155-199, 277-299 | |
| 208W | 26 | BW | IH | 4-0 | 31-41-23 | D00883A | A13 | | | | D00877 | 72 | | ALL | |
| 208WN | 26 | BW | IH | 0-0 | 31-41-23 | D00883A | B13 | | | | D00877 | 71 | | ALL | |
| 208Z | | | IH | 0-0 | 31-41-23 | GD00159 | S.. | 2 | | | D00877 | | ID | 050-099, 150-154, 275-276 | |
| 208Z | | | IH | 0-0 | 31-41-23 | GDX0001 | S.. | 2 | | | D00877 | | ID | 155-199, 277-299 | |
| 209W | 26 | BW | II | 4-0 | 31-41-23 | D00883A | A15 | | | | D00877 | 78 | | ALL | |
| 209WN | 26 | BW | II | 0-0 | 31-41-23 | D00883A | B15 | | | | D00877 | 77 | | ALL | |
| 209Z | | | II | 0-0 | 31-41-23 | GD00159 | S.. | 2 | | | D00877 | | IE | 050-099, 150-154, 275-276 | |
| 209Z | | | II | 0-0 | 31-41-23 | GDX0001 | S.. | 2 | | | D00877 | | IE | 155-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W1030

Page 10

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|--------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1037 | 286T1037 | | | E8 SHELF-EICAS LOWER DU SWITCHING MODULE (continued) | | | | | | | | | | | |
| 210W | 26 | BW | IJ | 3-0 | 31-41-23 | D05057J | | 12 | | | D00877 | | 4 | | ALL |
| 210WN | 26 | BW | IJ | 0-0 | 31-41-23 | D05057J | | 11 | | | D00877 | | 3 | | ALL |
| 210Z | | | IJ | 0-0 | 31-41-23 | D05057J | | 13 | | | D00877 | | | IB | ALL |
| 211W | 26 | BW | IK | 3-0 | 31-41-23 | D05057J | | 15 | | | D00877 | | 10 | | ALL |
| 211WN | 26 | BW | IK | 0-0 | 31-41-23 | D05057J | | 14 | | | D00877 | | 9 | | ALL |
| 211Z | | | IK | 0-0 | 31-41-23 | D05057J | | 16 | | | D00877 | | | IC | ALL |
| 212W | 26 | BW | IL | 3-0 | 31-41-23 | D05057J | | 18 | | | D00877 | | 16 | | ALL |
| 212WN | 26 | BW | IL | 0-0 | 31-41-23 | D05057J | | 17 | | | D00877 | | 15 | | ALL |
| 212Z | | | IL | 0-0 | 31-41-23 | D05057J | | 19 | | | D00877 | | | ID | ALL |
| 213W | 26 | BW | IM | 3-0 | 31-41-23 | D05057J | | 21 | | | D00877 | | 22 | | ALL |
| 213WN | 26 | BW | IM | 0-0 | 31-41-23 | D05057J | | 20 | | | D00877 | | 21 | | ALL |
| 213Z | | | IM | 0-0 | 31-41-23 | D05057J | | 22 | | | D00877 | | | IE | ALL |
| 214W | 26 | BW | IN | 4-0 | 31-41-24 | D00881A | | A11 | | | D00877 | | 44 | | ALL |
| 214WN | 26 | BW | IN | 0-0 | 31-41-24 | D00881A | | B11 | | | D00877 | | 43 | | ALL |
| 214Z | | | IN | 0-0 | 31-41-24 | GD00081 | | S.. | 2 | | D00877 | | | IN | 050-099, 150-154, 275-276 |
| 214Z | | | IN | 0-0 | 31-41-24 | GDX0002 | | S.. | 2 | | D00877 | | | IN | 155-199, 277-299 |
| 215W | 26 | BW | IO | 4-0 | 31-41-24 | D00881A | | A02 | | | D00877 | | 26 | | ALL |
| 215WN | 26 | BW | IO | 0-0 | 31-41-24 | D00881A | | A01 | | | D00877 | | 25 | | ALL |
| 215Z | | | IO | 0-0 | 31-41-24 | GD00081 | | S.. | 2 | | D00877 | | | IO | 050-099, 150-154, 275-276 |
| 215Z | | | IO | 0-0 | 31-41-24 | GDX0002 | | S.. | 2 | | D00877 | | | IO | 155-199, 277-299 |
| 216W | 26 | BW | IP | 4-0 | 31-41-24 | D00881B | | B03 | | | D00877 | | 32 | | ALL |
| 216WN | 26 | BW | IP | 0-0 | 31-41-24 | D00881B | | A03 | | | D00877 | | 31 | | ALL |
| 216Z | | | IP | 0-0 | 31-41-24 | GD00083 | | S.. | 2 | | D00877 | | | IP | 050-099, 150-154, 275-276 |
| 216Z | | | IP | 0-0 | 31-41-24 | GDX0002 | | S.. | 2 | | D00877 | | | IP | 155-199, 277-299 |
| 217W | 26 | BW | IQ | 4-0 | 31-41-24 | D00881B | | A04 | | | D00877 | | 38 | | ALL |
| 217WN | 26 | BW | IQ | 0-0 | 31-41-24 | D00881B | | B04 | | | D00877 | | 37 | | ALL |
| 217Z | | | IQ | 0-0 | 31-41-24 | GD00083 | | S.. | 2 | | D00877 | | | IQ | 050-099, 150-154, 275-276 |
| 217Z | | | IQ | 0-0 | 31-41-24 | GDX0002 | | S.. | 2 | | D00877 | | | IQ | 155-199, 277-299 |
| 218W | 26 | BW | IR | 4-0 | 31-41-24 | D00883A | | A11 | | | D00877 | | 102 | | ALL |
| 218WN | 26 | BW | IR | 0-0 | 31-41-24 | D00883A | | B11 | | | D00877 | | 101 | | ALL |
| 218Z | | | IR | 0-0 | 31-41-24 | GD00159 | | S.. | 2 | | D00877 | | | IN | 050-099, 150-154, 275-276 |
| 218Z | | | IR | 0-0 | 31-41-24 | GDX0001 | | S.. | 2 | | D00877 | | | IN | 155-199, 277-299 |
| 219W | 26 | BW | IS | 4-0 | 31-41-24 | D00883A | | A02 | | | D00877 | | 84 | | ALL |
| 219WN | 26 | BW | IS | 0-0 | 31-41-24 | D00883A | | A01 | | | D00877 | | 83 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1030
Page 11
Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|--------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1037 | 286T1037 | | | E8 SHELF-EICAS LOWER DU SWITCHING MODULE (continued) | | | | | | | | | | | | |
| 219Z | | | | IS | 0-0 | 31-41-24 | GD00159 | S.. | 2 | | D00877 | | | IO | 050-099, 150-154, 275-276 | |
| 219Z | | | | IS | 0-0 | 31-41-24 | GDX0001 | S.. | 2 | | D00877 | | | IO | 155-199, 277-299 | |
| 220W | 26 | | BW | IT | 4-0 | 31-41-24 | D00883B | B03 | | | D00877 | 90 | | | ALL | |
| 220WN | 26 | | BW | IT | 0-0 | 31-41-24 | D00883B | A03 | | | D00877 | 89 | | | ALL | |
| 220Z | | | | IT | 0-0 | 31-41-24 | GD00151 | S.. | 2 | | D00877 | | | IP | 050-099, 150-154, 275-276 | |
| 220Z | | | | IT | 0-0 | 31-41-24 | GDX0001 | S.. | 2 | | D00877 | | | IP | 155-199, 277-299 | |
| 221W | 26 | | BW | IU | 4-0 | 31-41-24 | D00883B | A04 | | | D00877 | 96 | | | ALL | |
| 221WN | 26 | | BW | IU | 0-0 | 31-41-24 | D00883B | B04 | | | D00877 | 95 | | | ALL | |
| 221Z | | | | IU | 0-0 | 31-41-24 | GD00151 | S.. | 2 | | D00877 | | | IQ | 050-099, 150-154, 275-276 | |
| 221Z | | | | IU | 0-0 | 31-41-24 | GDX0001 | S.. | 2 | | D00877 | | | IQ | 155-199, 277-299 | |
| 222W | 26 | | BW | IV | 3-0 | 31-41-24 | D05057J | | 24 | | D00877 | 46 | | | ALL | |
| 222WN | 26 | | BW | IV | 0-0 | 31-41-24 | D05057J | | 23 | | D00877 | 45 | | | ALL | |
| 222Z | | | | IV | 0-0 | 31-41-24 | D05057J | | 25 | | D00877 | | | IN | ALL | |
| 223W | 26 | | BW | IW | 3-0 | 31-41-24 | D05057J | | 27 | | D00877 | 28 | | | ALL | |
| 223WN | 26 | | BW | IW | 0-0 | 31-41-24 | D05057J | | 26 | | D00877 | 27 | | | ALL | |
| 223Z | | | | IW | 0-0 | 31-41-24 | D05057J | | 28 | | D00877 | | | IO | ALL | |
| 224W | 26 | | BW | IX | 3-0 | 31-41-24 | D05057J | | 30 | | D00877 | 34 | | | ALL | |
| 224WN | 26 | | BW | IX | 0-0 | 31-41-24 | D05057J | | 29 | | D00877 | 33 | | | ALL | |
| 224Z | | | | IX | 0-0 | 31-41-24 | D05057J | | 31 | | D00877 | | | IP | ALL | |
| 225W | 26 | | BW | IY | 3-0 | 31-41-24 | D05057J | | 33 | | D00877 | 40 | | | ALL | |
| 225WN | 26 | | BW | IY | 0-0 | 31-41-24 | D05057J | | 32 | | D00877 | 39 | | | ALL | |
| 225Z | | | | IY | 0-0 | 31-41-24 | D05057J | | 34 | | D00877 | | | IQ | ALL | |
| 226B | 24 | | PW | JA | 4-0 | 31-31-13 | D00881B | B09 | | | D00877 | 53 | | | 050-099, 275-299 | |
| 226B | 24 | | PW | JA | 3-0 | 31-31-13 | D00881B | B09 | | | D00877 | 53 | | | 150-199 | |
| 226R | 24 | | PW | JA | 0-0 | 31-31-13 | D00881B | A09 | | | D00877 | 52 | | | ALL | |
| 226Z | | | | JA | 0-0 | 31-31-13 | GD00083 | S.. | 2 | | D00877 | | | JA | 050-099, 150-154 | |
| 226Z | | | | JA | 0-0 | 31-31-13 | GDX0002 | S.. | 2 | | D00877 | | | JA | 155-199 | |
| 226Z | | | | JA | 0-0 | 31-31-13 | GD00083 | S.. | 2 | | D00877 | | REF | JA | 275-276 | |
| 226Z | | | | JA | 0-0 | 31-31-13 | GDX0002 | S.. | 2 | | D00877 | | REF | JA | 277-299 | |
| 227B | 24 | | PW | JB | 4-0 | 31-31-13 | D00883B | B09 | | | D00877 | 108 | | | ALL | |
| 227R | 24 | | PW | JB | 0-0 | 31-31-13 | D00883B | A09 | | | D00877 | 107 | | | ALL | |
| 227Z | | | | JB | 0-0 | 31-31-13 | GD00151 | S.. | 2 | | D00877 | | | JA | 050-099, 150-154 | |
| 227Z | | | | JB | 0-0 | 31-31-13 | GDX0001 | S.. | 2 | | D00877 | | | JA | 155-199 | |
| 227Z | | | | JB | 0-0 | 31-31-13 | GD00151 | S.. | 2 | | D00877 | | REF | JA | 275-276 | |
| 227Z | | | | JB | 0-0 | 31-31-13 | GDX0001 | S.. | 2 | | D00877 | | REF | JA | 277-299 | |
| 228B | 24 | | PW | JC | 3-0 | 31-31-13 | TB0237X | C007 | BJ | | D00877 | 55 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1030

Page 12

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1037 | 286T1037 | | | E8 SHELF-EICAS LOWER DU SWITCHING MODULE (continued) | | | | | | | | | | | |
| 228R | 24 | PW | JC | 0-0 | 31-31-13 | TB0237X | B007 | BJ | | D00877 | | 54 | | ALL | |
| 228Z | | | JC | 0-0 | 31-31-13 | TB0237X | D007 | BJ | | D00877 | | | JA | 050-099, 150-199 | |
| 228Z | | | JC | 0-0 | 31-31-13 | TB0237X | D007 | BJ | | D00877 | | REF | JA | 275-299 | |
| W1038 | 286T1038 | | | E6-R1-APU CONTROL | | | | | | | | | | | |
| 002 | 18 | PA | | 2-9 | 24-31-41 | D00298 | | 10 | | D06394P | | 2 | DK | ALL | |
| 003 | 18 | PA | | 2-9 | 24-31-41 | D00298 | | 7 | | D06394P | | 3 | DK | ALL | |
| 004 | 18 | PA | | 2-9 | 24-31-41 | D00298 | | 4 | | D06394P | | 4 | DK | ALL | |
| 005 | 20 | PA | | 6-0 | 24-31-41 | D00298 | | 8 | | GDX0001 | | D.. | 2 | ALL | |
| 006 | 20 | PA | | 6-0 | 24-31-41 | D00298 | | 2 | | GDX0001 | | S.. | 2 | 050-099, 150-155, 162-165, 275-276 | |
| 006 | 20 | PA | | 2-1 | 24-31-41 | D00298 | | 2 | | GD05962 | | S.. | E | 156-157, 166-199, 277-299 | |
| 007 | 24 | PK | | 7-10 | 24-31-41 | D00298 | | 1 | | D00302 | | 1 | | ALL | |
| 008 | 24 | PK | | 7-10 | 24-31-41 | D00298 | | 3 | | D00302 | | 3 | | ALL | |
| 009 | 24 | PK | | 7-10 | 24-31-41 | D00298 | | 11 | | D00302 | | 11 | | ALL | |
| 010 | 24 | PK | | 7-10 | 24-31-41 | D00298 | | 12 | | D00302 | | 12 | | ALL | |
| 011 | 20 | PA | | 9-4 | 24-31-41 | GDX0001 | | D.. | 2 | D00302 | | 9 | | ALL | |
| 012 | 24 | PK | | 9-3 | 24-31-41 | TB0026G | | 1 | 2 | D00302 | | 8 | | ALL | |
| 014 | 24 | PK | | 4-2 | 24-31-41 | TB0026G | | 1 | 2 | D06394P | | 16 | | ALL | |
| 017 | 20 | PA | | 4-2 | 36-11-41 | TB0026F | C004 | 2 | | D06394P | | 5 | | ALL | |
| 018 | 20 | PA | | 4-2 | 36-11-41 | TB0026F | A005 | 2 | | D06394P | | 6 | | ALL | |
| 019 | 24 | PK | | 4-2 | 36-11-41 | TB0026G | | 6 | 2 | D06394P | | 10 | | 150-157 | |
| 020 | 24 | PK | | 4-2 | 36-11-41 | TB0026F | C002 | 2 | | D06394P | | 8 | | ALL | |
| 021 | 24 | PK | | 4-2 | 36-11-41 | D06394P | | 7 | | TB0026F | A004 | 2 | | ALL | |
| 022 | 24 | PK | | 4-2 | 36-11-41 | D06394P | | 9 | | TB0026F | C005 | 2 | | ALL | |
| W1039 | 286T1039 | | | E8 SHELF-EICAS F/E DU SWITCHING MODULE | | | | | | | | | | | |
| 013 | 24 | PK | | 3-0 | 27-18-11 | D06968J | | 1 | | TB0239Y | A041 | BJ | | 155-157, 166-199, 277-299 | |
| 014 | 24 | PK | | 3-0 | 27-18-11 | D06968J | | 2 | | TB0239Y | C041 | BJ | | 155-157, 166-199, 277-299 | |
| 015 | 24 | PK | | 3-0 | 27-18-11 | D06968J | | 3 | | D06966J | | 3 | | 155-157, 166-199, 277-299 | |
| 016 | 24 | PK | | 3-0 | 27-18-11 | D06968J | | 4 | | D06966J | | 4 | | 155-157, 166-199, 277-299 | |
| 017 | 24 | PK | | 3-0 | 27-18-11 | D06968J | | 5 | | TB0239Y | A042 | BJ | | 155-157, 166-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W1030
Page 13
Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1039 | 286T1039 | | | E8 SHELF-EICAS F/E DU SWITCHING MODULE (continued) | | | | | | | | | | | | |
| 018 | 24 | | PK | 3-0 | 27-18-11 | D06968J | | 6 | | | TB0239Y | C042 | BJ | | 155-157, 166-199, 277-299 | |
| 019 | 24 | | PK | 4-0 | 27-18-11 | D06966J | | 1 | | | TB0239Y | A041 | BJ | | 155-157, 166-199, 277-299 | |
| 020 | 24 | | PK | 4-0 | 27-18-11 | D06966J | | 2 | | | TB0239Y | C041 | BJ | | 155-157, 166-199, 277-299 | |
| 021 | 24 | | PK | 4-0 | 27-18-11 | D06966J | | 5 | | | TB0239Y | A042 | BJ | | 155-157, 166-199, 277-299 | |
| 022 | 24 | | PK | 4-0 | 27-18-11 | D06966J | | 6 | | | TB0239Y | C042 | BJ | | 155-157, 166-199, 277-299 | |
| 023 | 24 | | PK | 4-0 | 27-18-11 | D06966J | | 7 | | | TB0239Y | A043 | BJ | | 155-157, 166-199, 277-299 | |
| 024 | 24 | | PK | 4-0 | 27-18-11 | D06966J | | 8 | | | TB0239Y | C043 | BJ | | 155-157, 166-199, 277-299 | |
| 025 | 24 | | PK | 4-0 | 27-18-11 | D06966J | | 10 | | | TB0239Y | A044 | BJ | | 155-157, 166-199, 277-299 | |
| 026 | 24 | | PK | 4-0 | 27-18-11 | D06966J | | 12 | | | TB0239Y | C044 | BJ | | 155-157, 166-199, 277-299 | |
| 027 | 24 | | PK | 3-0 | 27-18-11 | D06970J | | 1 | | | TB0239Y | A043 | BJ | | 155-157, 166-199, 277-299 | |
| 028 | 24 | | PK | 3-0 | 27-18-11 | D06970J | | 2 | | | TB0239Y | C043 | BJ | | 155-157, 166-199, 277-299 | |
| 029 | 24 | | PK | 3-0 | 27-18-11 | D06966J | | 9 | | | D06970J | | 3 | | 155-157, 166-199, 277-299 | |
| 030 | 24 | | PK | 3-0 | 27-18-11 | D06970J | | 4 | | | TB0239Y | A044 | BJ | | 155-157, 166-199, 277-299 | |
| 031 | 24 | | PK | 3-0 | 27-18-11 | D06966J | | 11 | | | D06970J | | 5 | | 155-157, 166-199, 277-299 | |
| 032 | 24 | | PK | 3-0 | 27-18-11 | D06970J | | 6 | | | TB0239Y | C044 | BJ | | 155-157, 166-199, 277-299 | |
| 033 | 24 | | PK | 3-0 | 27-28-11 | D06966J | | 13 | | | D06980J | | 1 | | 155-157, 166-199, 277-299 | |
| 034 | 24 | | PK | 3-0 | 27-28-11 | D06966J | | 14 | | | D06980J | | 2 | | 155-157, 166-199, 277-299 | |
| 035 | 24 | | PK | 3-0 | 27-28-11 | D06966J | | 15 | | | D06980J | | 3 | | 155-157, 166-199, 277-299 | |
| 036 | 24 | | PK | 3-0 | 27-38-11 | D06966J | | 16 | | | D06980J | | 4 | | 155-157, 166-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W1030

Page 14

Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1039 | 286T1039 | | | E8 SHELF-EICAS F/E DU SWITCHING MODULE (continued) | | | | | | | | | | | |
| 037 | 24 | | PK | 3-0 | 27-38-11 | D06966J | | 17 | | D06980J | | 5 | | 155-157, 166-199, 277-299 | |
| 038 | 24 | | PK | 3-0 | 27-38-11 | D06966J | | 18 | | D06980J | | 6 | | 155-157, 166-199, 277-299 | |
| 039 | 24 | | PK | 3-0 | 27-38-11 | D06966J | | 19 | | D06980J | | 7 | | 155-157, 166-199, 277-299 | |
| 040 | 24 | | PK | 3-0 | 27-38-11 | D06966J | | 20 | | D06980J | | 8 | | 155-157, 166-199, 277-299 | |
| 041 | 24 | | PK | 3-0 | 27-38-11 | D06966J | | 21 | | D06980J | | 9 | | 155-157, 166-199, 277-299 | |
| 042 | 24 | | PK | 3-0 | 27-48-11 | D06966J | | 33 | | D06980J | | 10 | | 157, 167-199, 277-299 | |
| 043 | 24 | | PK | 3-0 | 27-48-11 | D06966J | | 32 | | D06980J | | 11 | | 157, 167-199, 277-299 | |
| 044 | 20 | | PA | 3-0 | 27-48-11 | D06966J | | 34 | | GDX0001 | | A.. | 2 | 157, 167-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W1030
Page 15 End
Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---------------------------------------|----------|---------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1040 | 286T1040 | | | P6-S1-STANDBY PWR DISTRIBUTION | | | | | | | | | | | |
| 001 | 06 | HA | | 5-0 | 24-31-11 | TB5014 | | 2 | G | | C00896 | 1 | F | | ALL |
| 002 | 08 | PA | | 5-0 | 24-33-11 | K00104 | | B1 | E2 | * | C00814 | 2 | D | | ALL |
| 003 | 06 | PA | | 2-0 | 24-33-11 | K00106 | | A1 | E | | K00104 | A2 | E | | ALL |
| 004 | 06 | PA | | 5-0 | 24-33-11 | C00813 | | 1 | F | | K00104 | A1 | E | | ALL |
| 005 | 08 | PA | | 5-0 | 24-33-11 | C00898 | | 1 | D | | K00104 | B1 | E2 | * | ALL |
| 006 | 08 | PA | | 4-0 | 24-33-11 | C00872 | | 1 | D | | K00104 | B2 | E2 | * | ALL |
| 007 | 08 | PA | | 2-0 | 24-33-11 | K00106 | | B1 | E2 | * | K00104 | B2 | E2 | * | ALL |
| 008 | 08 | PA | | 4-0 | 24-54-71 | K00106 | | B1 | E2 | * | D04094J | A | | | ALL |
| 009 | 12 | PA | | 2-0 | 24-54-71 | C00829 | | 2 | D | | C00828 | 1 | D | * | ALL |
| 010 | 12 | PA | | 1-0 | 24-54-71 | C00806 | | 2 | D | * | C00828 | 1 | D | * | ALL |
| 012 | 08 | PA | | 8-0 | 24-54-72 | C00897 | | 1 | D | | C00800 | 1 | LA | * | ALL |
| 013 | 08 | PA | | 1-0 | 24-54-72 | C00779 | | 2 | D | | C04217 | 1 | LA | * | 050-099 |
| 013 | 08 | PA | | 1-0 | 24-54-72 | C00779 | | 2 | D | | C00576 | 1 | LA | * | 150-199, 275-299 |
| 014 | 08 | PA | | 2-0 | 24-54-72 | C04217 | | 1 | LA | * | C01179 | 2 | LA | * | 050-099 |
| 014 | 08 | PA | | 2-0 | 24-54-72 | C00576 | | 1 | LA | * | C01179 | 2 | LA | * | 150-199, 275-299 |
| 015 | 08 | PA | | 1-0 | 24-54-72 | C01179 | | 2 | LA | * | C01062 | 1 | LA | * | ALL |
| 016 | 08 | PA | | 2-0 | 24-54-72 | C01062 | | 1 | LA | * | C00827 | 2 | LA | * | ALL |
| 017 | 12 | PA | | 5-0 | 24-54-73 | D04096J | | 16 | | | TB5012 | 3 | C | * | ALL |
| 018 | 14 | PA | | 5-0 | 24-54-73 | D04096J | | 14 | | | D03252 | C3 | | | ALL |
| 021 | 18 | PA | | 5-0 | 24-51-31 | D04096J | | 18 | | | TB0014F | A008 | 2 | | ALL |
| 022 | 22 | PA | | 6-0 | 24-51-31 | D04096J | | 1 | | | TB0014G | 11 | 2 | | ALL |
| 023 | 14 | PA | | 6-0 | 24-33-11 | C00872 | | 2 | D | | D03252 | A2 | | | ALL |
| 024 | 16 | PA | | 3-0 | 24-33-11 | D00324 | | 7 | | | D03252 | C2 | | | ALL |
| 025 | 16 | PA | | 5-0 | 24-33-11 | D00324 | | 10 | | | TB5012 | 1 | C | * | ALL |
| 026 | 14 | PA | | 2-0 | 24-33-11 | D04124J | | 1 | | | TB5012 | 1 | C | * | ALL |
| 027 | 18 | PA | | 5-0 | 24-33-11 | D00324 | | 4 | | | TB5012 | 2 | C | * | ALL |
| 028 | 18 | PA | | 5-0 | 24-33-11 | D00324 | | 1 | DK | | TB5012 | 2 | C | * | ALL |
| 033 | 20 | PA | | 2-0 | 24-33-11 | D00324 | | 2 | | | TB0014F | C003 | 2 | | ALL |
| 034 | 24 | PK | | 3-0 | 24-33-11 | D03252 | | X2 | | | TB0014F | A004 | 2 | | ALL |
| 035 | 24 | PV | A | 6-0 | 24-33-11 | D03252 | | X1 | | | C00828 | 2 | D | | ALL |
| 035Z | | | A | 0-0 | 24-33-11 | D03252 | | DED | | | C00828 | DED | | | ALL |
| 037 | 08 | PA | | 1-0 | 24-54-72 | C00827 | | 2 | LA | * | C00614 | 2 | LA | * | ALL |
| 038 | 08 | PA | | 1-0 | 24-54-72 | C00614 | | 2 | LA | * | C01089 | 1 | LA | * | ALL |
| 039 | 08 | PA | | 1-0 | 24-54-72 | C01089 | | 1 | LA | * | C00800 | 1 | LA | * | ALL |
| 040 | 08 | PA | | 5-0 | 29-21-31 | TB5014 | | 3 | G | | C01088 | 1 | D | | ALL |
| 042 | 24 | PK | | 5-0 | 24-51-31 | D04096J | | 2 | | | TB0014G | 9 | 2 | | ALL |
| 044 | 12 | PA | | 2-0 | 24-54-71 | C00806 | | 2 | D | * | C01100 | 1 | D | | ALL |
| 045 | 24 | PK | | 2-0 | 24-33-11 | D00324 | | 5 | | | TB0014G | 13 | 2 | | ALL |
| 046 | 24 | PK | | 2-0 | 24-33-11 | D00324 | | 6 | | | TB0014G | 14 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1040

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1040 | 286T1040 | | | P6-S1-STANDBY PWR DISTRIBUTION (continued) | | | | | | | | | | | |
| 047 | 12 | | PA | 2-0 | 24-54-71 | C00809 | 2 | D | | C04248 | 2 | D | | ALL | |
| 059 | 12 | | PA | 8-0 | 24-54-73 | TB5012 | 3 | C | * | D03252 | A3 | | | ALL | |
| W1042 | 286T1042 | | | P6-S1-MAIN BATT PWR DISTRIBUTION | | | | | | | | | | | |
| 001 | 06 | | HA | 5-0 | 24-31-11 | TB5014 | 1 | Q | * | C00896 | 2 | F | * | 050-099, 150-154, 162-163, 275-276 | |
| 001 | 06 | | HA | 3-6 | 24-31-11 | TB5014 | 1 | Q | * | C00830 | 2 | M | | 155-157, 164-199, 277-299 | |
| 002 | 06 | | HA | 2-0 | 24-31-11 | C00830 | 2 | D | | C00896 | 2 | F | * | 050-099, 150-154, 162-163, 275-276 | |
| 003 | 06 | | HA | 5-0 | 24-31-11 | TB5014 | 1 | Q | * | C00813 | 2 | F | * | 050-099, 150-154, 162-163, 275-276 | |
| 003 | 06 | | HA | 1-0 | 24-31-11 | C01088 | 2 | M | | C00813 | 2 | F3 | | 155-157, 164-199, 277-299 | |
| 004 | 06 | | HA | 2-0 | 24-31-11 | C00896 | 2 | F | * | C00898 | 2 | E9 | * | 050-099, 150-154, 162-163, 275-276 | |
| 004 | 06 | | HA | 0-11 | 24-31-11 | C00896 | 2 | F3 | | C00898 | 2 | M | | 155-157, 164-199, 277-299 | |
| 005 | 06 | | HA | 2-0 | 24-31-11 | C01088 | 2 | D | | C00898 | 2 | E9 | * | 050-099, 150-154, 162-163, 275-276 | |
| 005 | 06 | | HA | 3-8 | 24-31-11 | C01088 | 2 | M | | TB5014 | 1 | Q | * | 155-157, 164-199, 277-299 | |
| 006 | 06 | | HA | 2-0 | 24-31-11 | C00813 | 2 | F | * | C00897 | 2 | D | | 050-099, 150-154, 162-163, 275-276 | |
| 006 | 06 | | HA | 0-11 | 24-31-11 | C00813 | 2 | F3 | | C00896 | 2 | F3 | | 155-157, 164-199, 277-299 | |
| 007 | 06 | | HA | 2-4 | 24-31-11 | C00897 | 2 | M | | C00830 | 2 | M | | 155-157, 164-199, 277-299 | |
| 009 | 06 | | HA | 5-0 | 24-31-11 | C00830 | 2 | D | | TB5014 | 1 | Q | * | 050-099 | |
| 009 | 06 | | HA | 5-0 | 24-31-11 | TB5014 | 1 | Q | * | C00830 | 2 | D | | 150-154, 162-163, 275-276 | |
| 010 | 06 | | HA | 5-0 | 24-31-11 | TB5014 | 4 | Q | | C00830 | 1 | D | | 050-099 | |
| 010 | 06 | | HA | 5-0 | 24-31-11 | C00830 | 1 | D | | TB5014 | 4 | Q | | 150-154, 162-163, 275-276 | |
| 010 | 06 | | HA | 4-1 | 24-31-11 | C00830 | 1 | M | | TB5014 | 4 | Q | | 155-157, 164-199, 277-299 | |
| W1043 | 286T1043 | | | COAX-SATCOM,M1782 HPA TO AP1101 (LNA OR HPR) | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-17 | D02651B | = | C71 | | D06183J | = | C1 | | 156-157, 166-199 | |

WIRE LIST
D280T132

91-21-11
Section W1040
Page 2
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|--------|---------|------|------|--------|--------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1043 | 286T1043 | | | | COAX-SATCOM,M1782 HPA TO AP1101 (LNA OR HPR) (continued) | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-16 | D02651B | = C71 | | | | D06183J | = C1 | | | 277-299 | |
| 01CX | | 78 | A | 1-0 | 23-25-17 | D02651B | 71 | | | | D06183J | = A1 | | | 156-157, 166-199 | |
| 01CX | | JB | A | 1-0 | 23-25-16 | D02651B | 71 | | | | D06183J | = A1 | | | 277-299 | |
| W1044 | 286T1044 | | | | P36-L1-POWER DISTRIBUTION | | | | | | | | | | | |
| 001 | 10 | | HA | 1-0 | 24-51-12 | C00334 | A2 | M | * | | C00375 | A1 | M | * | 050-099 | |
| 002 | 10 | | HA | 1-0 | 24-51-12 | C00334 | B2 | M | * | | C00375 | B1 | M | * | 050-099 | |
| 003 | 10 | | HA | 1-0 | 24-51-12 | C00334 | C2 | M | * | | C00375 | C1 | M | * | 050-099 | |
| 007 | 10 | | HA | 6-0 | 24-51-12 | TB5130 | 1 | N | | | C00389 | A1 | M | * | ALL | |
| 008 | 10 | | HA | 6-0 | 24-51-12 | TB5130 | 2 | N | | | C00389 | B1 | M | * | ALL | |
| 009 | 10 | | HA | 6-0 | 24-51-12 | TB5130 | 3 | N | | | C00389 | C1 | M | * | 050-099 | |
| 009 | 08 | | HA | 6-0 | 24-51-12 | TB5130 | 3 | N | | | C00389 | C1 | M | * | 150-199, 275-299 | |
| 010 | 10 | | HA | 7-0 | 24-51-13 | TB5130 | 4 | N | | | C00336 | A1 | M | * | 050-099, 150-199 | |
| 010 | 10 | | HA | 7-0 | 24-51-13 | TB5130 | 4 | N | | | C01129 | A1 | M | | 275-299 | |
| 011 | 10 | | HA | 7-0 | 24-51-13 | TB5130 | 8 | N | | | C00336 | B1 | M | * | 050-099, 150-199 | |
| 011 | 10 | | HA | 7-0 | 24-51-13 | TB5130 | 5 | N | | | C01129 | B1 | M | | 275-299 | |
| 012 | 10 | | HA | 7-0 | 24-51-13 | TB5130 | 6 | N | | | C00336 | C1 | M | * | 050-099, 150, 152-199 | |
| 012 | 10 | | HA | 7-0 | 24-51-13 | TB5130 | 6 | N | | | C00336 | C1 | M | | 151 | |
| 012 | 10 | | HA | 7-0 | 24-51-13 | TB5130 | 6 | N | | | C01129 | C1 | M | | 275-299 | |
| 013 | 10 | | HA | 2-0 | 24-51-12 | C00389 | A1 | M | * | | C00334 | A2 | M | * | 150-157, 165-199, 275, 277-299 | |
| 013 | 10 | | HA | 5-0 | 24-51-12 | C00389 | A1 | M | * | | C00375 | A1 | M | * | 162-164, 276 | |
| 014 | 10 | | HA | 2-0 | 24-51-12 | C00389 | B1 | M | * | | C00334 | B2 | M | * | 150-157, 165-199, 275, 277-299 | |
| 014 | 10 | | HA | 5-0 | 24-51-12 | C00389 | B1 | M | * | | C00375 | B1 | M | * | 162-164, 276 | |
| 015 | 08 | | HA | 2-0 | 24-51-12 | C00389 | C1 | M | * | | C00334 | C2 | M | * | 150-157, 165-199, 275, 277-299 | |
| 015 | 08 | | HA | 5-0 | 24-51-12 | C00389 | C1 | M | * | | C00375 | C1 | M | * | 162-164, 276 | |
| 016 | 12 | | HA | 2-0 | 24-51-12 | C00334 | A2 | M | * | | C00391 | A2 | M | | 050-099 | |
| 016 | 12 | | HA | 4-0 | 24-51-12 | C00334 | A2 | M | * | | C00391 | A2 | M | * | 150-154, 275 | |
| 016 | 12 | | HA | 4-0 | 24-51-12 | C00334 | A2 | M | * | | C00391 | A2 | M | * | 155-199, 276-299 | |
| 017 | 12 | | HA | 2-0 | 24-51-12 | C00334 | B2 | M | * | | C00391 | B2 | M | * | 050-099 | |
| 017 | 12 | | HA | 4-0 | 24-51-12 | C00334 | B2 | M | * | | C00391 | B2 | M | * | 150-154 | |
| 017 | 12 | | HA | 4-0 | 24-51-12 | C00334 | B2 | M | * | | C00391 | B2 | M | * | 155-199, 275-299 | |
| 018 | 12 | | HA | 3-0 | 24-51-12 | C00334 | C2 | M | * | | C01125 | 1 | M | * | 050-099 | |
| 018 | 10 | | HA | 3-0 | 24-51-12 | C00334 | C2 | M | * | | C01125 | 1 | M | * | 150-199, 275-299 | |
| 019 | 12 | | HA | 3-0 | 24-51-12 | C01125 | 1 | M | * | | C00696 | 2 | M | * | 050-099, 155-199, 276-299 | |
| 019 | 12 | | HA | 2-0 | 24-51-12 | C01125 | 1 | M | * | | C00535 | 2 | M | * | 150-154, 275 | |

WIRE LIST

D280T132

91-21-11

Section W1040

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1044 | 286T1044 | | | P36-L1-POWER DISTRIBUTION (continued) | | | | | | | | | | | | |
| 020 | 14 | HA | | 2-0 | 24-51-12 | C00696 | 2 | M | * | C01341 | 2 | M | | ALL | | |
| 024 | 12 | HA | | 2-0 | 24-51-13 | C01365 | 1 | M | * | C00734 | 1 | M | * | 150-199 | | |
| 025 | 12 | HA | | 2-0 | 24-51-12 | C00546 | 2 | M | * | C00541 | 2 | M | | 050-099 | | |
| 025 | 12 | HA | | 2-0 | 24-51-12 | C00546 | 2 | M | * | C00533 | 2 | M | | 150-199, 275-299 | | |
| 027 | 10 | HA | | 2-0 | 24-51-13 | C00734 | 1 | M | * | C01365 | 1 | M | * | 050-099 | | |
| 027 | 12 | HA | | 6-0 | 24-51-13 | TB5130 | 8 | N | | C00734 | 1 | M | * | 150-199 | | |
| 027 | 12 | HA | | 2-0 | 24-51-13 | C00734 | 1 | M | * | C01365 | 1 | M | * | 275-299 | | |
| 028 | 12 | HA | | 4-0 | 24-51-13 | C01365 | 1 | M | * | C00663 | 1 | M | * | 050-099 | | |
| 028 | 12 | HA | | 3-0 | 24-51-13 | C01365 | 1 | M | * | C00663 | 1 | M | * | 150-199 | | |
| 028 | 12 | HA | | 3-0 | 24-51-13 | C01365 | 1 | M | * | C00663 | 1 | M | | 275-299 | | |
| 02A | 12 | HA | | 6-0 | 24-51-13 | TB5130 | 8 | N | | C00734 | 1 | M | * | 275-299 | | |
| 031 | 12 | HA | | 2-0 | 24-51-12 | C01127 | 1 | M | * | C00535 | 2 | M | | 050-099 | | |
| 031 | 12 | HA | | 3-0 | 24-51-12 | C00696 | 2 | M | * | C00535 | 2 | M | * | 150-154, 275 | | |
| 031 | 12 | HA | | 1-0 | 24-51-12 | C01127 | 1 | M | * | C00535 | 2 | M | | 155-199, 276-299 | | |
| 034 | 14 | HA | | 5-0 | 24-51-12 | TB5130 | 2 | N | | L00571 | 1 | L | | ALL | | |
| 035 | 14 | HA | | 4-0 | 24-51-12 | L00571 | 2 | L | | GDX0010 | A.. | P | | ALL | | |
| 036 | 14 | HA | | 5-0 | 24-51-13 | TB5130 | 5 | N | | L00572 | 1 | L | | ALL | | |
| 037 | 14 | HA | | 4-0 | 24-51-13 | L00572 | 2 | L | | GDX0010 | A.. | P | | ALL | | |
| 038 | 10 | HA | | 7-0 | 24-51-13 | TB5130 | 4 | N | | C00662 | 1 | M | * | 050-099 | | |
| 038 | 12 | HA | | 7-0 | 24-51-13 | TB5130 | 4 | N | | C00662 | 1 | M | * | 150-199 | | |
| 038 | 12 | HA | | 7-0 | 24-51-13 | TB5130 | 4 | N | | C00662 | 1 | M | | 275-299 | | |
| 045 | 10 | HA | | 2-0 | 24-51-13 | TB5130 | 5 | N | | TB5130 | 8 | N | | ALL | | |
| 046 | 12 | HA | | 3-0 | 24-51-12 | C00546 | 2 | M | * | C00391 | A2 | M | * | 150-154, 275 | | |
| 046 | 12 | HA | | 12-0 | 24-51-12 | C00546 | 2 | M | * | K02091 | A3 | N | | 155-199, 276-299 | | |
| 051 | 12 | HA | | 4-0 | 24-51-13 | C00336 | A1 | M | * | C00343 | A1 | M | * | 050-099, 150, 152-199 | | |
| 051 | 12 | HA | | 4-0 | 24-51-13 | C00336 | A1 | M | * | C00343 | A1 | M | | 151, 275-299 | | |
| 052 | 12 | HA | | 4-0 | 24-51-13 | C00336 | B1 | M | * | C00343 | B1 | M | * | 050-099, 150, 152-199 | | |
| 052 | 12 | HA | | 4-0 | 24-51-13 | C00336 | B1 | M | * | C00343 | B1 | M | | 151, 275-299 | | |
| 071 | 10 | HA | | 3-0 | 24-51-12 | C00375 | A1 | M | * | C00389 | A1 | M | * | 050-099 | | |
| 072 | 10 | HA | | 3-0 | 24-51-12 | C00375 | B1 | M | * | C00389 | B1 | M | * | 050-099 | | |
| 073 | 10 | HA | | 3-0 | 24-51-12 | C00375 | C1 | M | * | C00389 | C1 | M | * | 050-099 | | |
| 083 | 12 | HA | | 2-0 | 24-51-12 | C00534 | 2 | M | | C00391 | B2 | M | * | 050-099, 275-276 | | |
| 083 | 12 | HA | | 2-0 | 24-51-12 | C00391 | B2 | N1 | | C00534 | 2 | M | | 150-154 | | |
| 083 | 12 | HA | | 3-0 | 24-51-12 | C00391 | B2 | M | * | C00534 | 2 | M | | 155-157, 166-199, 277-299 | | |
| 083 | 12 | HA | | 2-0 | 24-51-12 | C00391 | B2 | M | * | C00534 | 2 | M | | 162-165 | | |
| 086 | 12 | HA | | 5-0 | 24-51-13 | C00342 | A2 | M | | C00662 | 1 | M | * | 150-199 | | |
| 087 | 12 | HA | | 5-0 | 24-51-13 | C00342 | B2 | M | | C00663 | 1 | M | * | 150-199 | | |
| 088 | 12 | HA | | 6-0 | 24-51-13 | C00342 | C2 | M | | TB5130 | 6 | N | | 150-199 | | |

WIRE LIST

D280T132

91-21-11

Section W1040

Page 4

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|--------|--------|---|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1044 | 286T1044 | | | P36-L1-POWER DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 091 | 12 | | HA | 9-0 | 24-51-12 | TB5130 | | 1 | N | | | | K02091 | A2 | N | | 155-199, 276-299 |
| 093 | 12 | | HA | 9-0 | 24-51-12 | TB5130 | | 3 | N | | | | K02091 | C2 | N | | 155-199, 276-299 |
| 094 | 10 | | HA | 12-0 | 24-51-12 | C00375 | | A1 | M | | | | K02091 | A1 | N | | 155, 165 |
| 094 | 12 | | HA | 12-0 | 24-51-12 | C00375 | | A1 | M | | | | K02091 | A1 | N | | 156-157, 166-199, 277-299 |
| 094 | 10 | | HA | 5-0 | 24-51-12 | C00375 | | A1 | M | * | | | C00334 | A2 | M | * | 162-164, 276 |
| 095 | 10 | | HA | 12-0 | 24-51-12 | C00375 | | B1 | M | | | | K02091 | B1 | N | | 155, 165 |
| 095 | 12 | | HA | 12-0 | 24-51-12 | C00375 | | B1 | M | | | | K02091 | B1 | N | | 156-157, 166-199, 277-299 |
| 095 | 10 | | HA | 5-0 | 24-51-12 | C00375 | | B1 | M | * | | | C00334 | B2 | M | * | 162-164, 276 |
| 096 | 08 | | HA | 12-0 | 24-51-12 | C00375 | | C1 | M | | | | K02091 | C1 | N | | 155, 165 |
| 096 | 12 | | HA | 12-0 | 24-51-12 | C00375 | | C1 | M | | | | K02091 | C1 | N | | 156-157, 166-199, 277-299 |
| 096 | 08 | | HA | 5-0 | 24-51-12 | C00375 | | C1 | M | * | | | C00334 | C2 | M | * | 162-164, 276 |
| 097 | 12 | | HA | 12-0 | 24-51-12 | C01127 | | 1 | M | * | | | K02091 | C3 | N | | 155-199, 276-299 |
| 101 | 12 | | HA | 9-0 | 24-51-12 | TB5130 | | 1 | N | | | | K02091 | A2 | N | | 050-099 |
| 102 | 12 | | HA | 9-0 | 24-51-12 | TB5130 | | 3 | N | | | | K02091 | C2 | N | | 050-099 |
| 103 | 12 | | HA | 12-0 | 24-51-12 | K02091 | | A3 | N | | | | C00546 | 2 | M | * | 050-099 |
| 104 | 12 | | HA | 12-0 | 24-51-12 | K02091 | | C3 | N | | | | C01127 | 1 | M | * | 050-099 |
| 105 | 12 | | HA | 4-0 | 24-51-13 | C00342 | | A2 | M | | | | C00662 | 1 | M | * | 050-099 |
| 106 | 12 | | HA | 4-0 | 24-51-13 | C00342 | | B2 | M | | | | C00663 | 1 | M | * | 050-099 |
| 107 | 10 | | HA | 7-0 | 24-51-13 | C00734 | | 1 | M | * | | | TB5130 | 8 | N | | 050-099 |
| 108 | 10 | | HA | 7-0 | 24-51-13 | C00342 | | C2 | M | | | | TB5130 | 6 | N | | 050-099 |
| 130 | 12 | | HA | 9-0 | 24-51-12 | TB5130 | | 2 | N | | | | K02091 | B2 | N | | 155-157, 165-199, 277-299 |
| 150 | 10 | | HA | 7-0 | 24-51-13 | C00336 | | A1 | M | * | | | C01129 | A1 | M | | 275-299 |
| 151 | 10 | | HA | 7-0 | 24-51-13 | C00336 | | B1 | M | * | | | C01129 | B1 | M | | 275-299 |
| 152 | 10 | | HA | 7-0 | 24-51-13 | C00336 | | C1 | M | | | | C01129 | C1 | M | | 275-299 |
| 501 | 12 | | HA | 3-0 | 24-51-13 | C00406 | | B1 | M | * | | | C00403 | B1 | M | * | 050-099, 162-199 |
| 501 | 12 | | HA | 3-0 | 24-51-13 | C00406 | | B1 | M | * | | | C00403 | B1 | M | | 150, 152-157 |
| 502 | 12 | | HA | 3-0 | 24-51-13 | C00406 | | A1 | M | * | | | C00403 | A1 | M | * | 050-099, 162-199 |
| 502 | 12 | | HA | 3-0 | 24-51-13 | C00406 | | A1 | M | * | | | C00403 | A1 | M | | 150, 152-157 |
| 503 | 12 | | HA | 3-0 | 24-51-13 | C00406 | | C1 | M | * | | | C00403 | C1 | M | * | 050-099, 162-199 |
| 503 | 12 | | HA | 3-0 | 24-51-13 | C00406 | | C1 | M | * | | | C00403 | C1 | M | | 150, 152-157 |
| 504 | 12 | | HA | 3-0 | 24-51-13 | C00400 | | B2 | M | * | | | C00403 | B1 | M | * | 050-099, 162-199 |
| 505 | 12 | | HA | 3-0 | 24-51-13 | C00400 | | A2 | M | * | | | C00403 | A1 | M | * | 050-099, 162-199 |
| 506 | 12 | | HA | 3-0 | 24-51-13 | C00400 | | C2 | M | * | | | C00403 | C1 | M | * | 050-099, 162-199 |
| 507 | 12 | | HA | 3-0 | 24-51-13 | C00400 | | B2 | M | * | | | C00401 | B2 | M | | 050-099, 162-199 |
| 508 | 12 | | HA | 3-0 | 24-51-13 | C00400 | | A2 | M | * | | | C00401 | A2 | M | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W1040

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1044 | 286T1044 | | | P36-L1-POWER DISTRIBUTION (continued) | | | | | | | | | | | |
| 509 | 12 | | HA | | 3-0 | 24-51-13 | C00400 | C2 | M | * | C00401 | C2 | M | | 050-099, 162-199 |
| 510 | 10 | | HA | | 6-0 | 24-54-11 | TB5130 | 7 | N | | C00915 | 1 | M | | 050-099, 162-199 |
| 510 | 10 | | HA | | 6-0 | 24-54-11 | TB5130 | 7 | N | | C00922 | 1 | M | | 155-156 |
| 511 | 12 | | HA | | 4-0 | 24-51-13 | C00406 | A1 | M | * | C00343 | A1 | M | * | 050-099, 150, 152-199 |
| 512 | 12 | | HA | | 4-0 | 24-51-13 | C00406 | C1 | M | * | C00336 | C1 | M | * | 050-099, 150, 152-199 |
| 570 | 12 | | HA | | 4-0 | 24-51-13 | C00406 | B1 | M | * | C00343 | B1 | M | * | 050-099, 150, 152-199 |
| 907 | 16 | | PA | | 5-0 | 24-51-13 | TB5130 | 4 | E | | C09033 | A1 | D | | 150, 153-199 |
| 908 | 16 | | PA | | 5-0 | 24-51-13 | TB5130 | 5 | E | | C09033 | B1 | D | | 150, 153-199 |
| 909 | 16 | | PA | | 5-0 | 24-51-13 | TB5130 | 6 | E | | C09033 | C1 | D | | 150, 153-199 |
| W1045 | 286T1045 | | | COAX-SATCOM,M1783 HPA TO AP1101 (LNA/DIP) | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-11 | D06181J | =C1 | | | D02653B | =C71 | | | 156-157, 166-199, 277-299 |
| 01CX | | | | JB A | 1-0 | 23-25-11 | D06181J | =A1 | | | D02653B | 71 | | | 156-157, 166-199, 277-299 |
| W1046 | 286T1046 | | | P37-R1-POWER DISTRIBUTION | | | | | | | | | | | |
| 007 | 10 | | HA | | 8-9 | 24-51-22 | TB5132 | 1 | N | | C00388 | A2 | M | * | ALL |
| 008 | 10 | | HA | | 8-9 | 24-51-22 | TB5132 | 2 | N | | C00388 | B2 | M | * | ALL |
| 009 | 10 | | HA | | 8-9 | 24-51-22 | TB5132 | 3 | N | | C00388 | C2 | M | * | ALL |
| 010 | 10 | | HA | | 8-11 | 24-51-23 | TB5132 | 4 | N | *1 | C00337 | A2 | D | * | 050-099, 162-165 |
| 010 | 10 | | HA | | 8-11 | 24-51-23 | TB5132 | 4 | N | *1 | C00337 | A2 | M | * | 150, 152-157, 166-199 |
| 010 | 10 | | HA | | 8-11 | 24-51-23 | TB5132 | 4 | N | *1 | C00337 | A2 | M | | 151, 275-299 |
| 011 | 10 | | HA | | 8-11 | 24-51-23 | TB5132 | 5 | N | | C00337 | B2 | D | * | 050-099, 162-165 |
| 011 | 10 | | HA | | 8-11 | 24-51-23 | TB5132 | 5 | N | | C00337 | B2 | M | * | 150, 152-157, 166-199 |
| 011 | 10 | | HA | | 8-11 | 24-51-23 | TB5132 | 5 | N | | C00337 | B2 | M | | 151, 275-299 |
| 012 | 10 | | HA | | 8-11 | 24-51-23 | TB5132 | 6 | N | | C00337 | C2 | D | * | 050-099, 162-165 |
| 012 | 10 | | HA | | 8-11 | 24-51-23 | TB5132 | 6 | N | | C00337 | C2 | M | * | 150, 152-157, 166-199 |
| 012 | 10 | | HA | | 8-11 | 24-51-23 | TB5132 | 6 | N | | C00337 | C2 | M | | 151, 275-299 |
| 013 | 12 | | HA | | 2-3 | 24-51-22 | C00376 | A1 | M | * | C00344 | A2 | D | * | 050-099 |
| 013 | 12 | | HA | | 1-11 | 24-51-22 | C00388 | A2 | M | * | C00344 | A2 | M | * | 150-154, 275 |
| 013 | 12 | | HA | | 7-3 | 24-51-22 | C00376 | A1 | M | | K02092 | A1 | N | | 155-157, 165-199, 277-299 |
| 013 | 12 | | HA | | 2-3 | 24-51-22 | C00376 | A1 | M | * | C00344 | A2 | M | * | 162-164, 276 |
| 014 | 12 | | HA | | 2-10 | 24-51-22 | C01124 | 2 | M | | C00359 | A2 | D | * | 050-099 |
| 014 | 12 | | HA | | 2-9 | 24-51-22 | C00359 | A2 | M | * | C01126 | 2 | M | | 150-154 |
| 014 | 12 | | HA | | 2-10 | 24-51-22 | C00359 | A2 | M | * | C01124 | 2 | M | | 155-199 |
| 014 | 12 | | HA | | 2-3 | 24-51-22 | C00359 | A2 | M | * | C01126 | 2 | M | | 275 |
| 014 | 12 | | HA | | 2-4 | 24-51-22 | C00359 | A2 | M | * | C01124 | 2 | M | | 276-299 |

WIRE LIST

D280T132

91-21-11

Section W1040

Page 6

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|--------|--------|-------------|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1046 | 286T1046 | | | P37-R1-POWER DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 015 | 12 | | HA | 7-2 | 24-51-22 | C00543 | | 1 | M | | | | K02092 | B3 | N | | 050-099 |
| 015 | 12 | | HA | 10-3 | 24-51-22 | TB5132 | | 1 | N | | | | C00543 | 1 | M | | 150-154 |
| 015 | 12 | | HA | 7-2 | 24-51-22 | K02092 | | | B3 | N | | | C00543 | 1 | M | | 155-199 |
| 015 | 12 | | HA | 2-2 | 24-51-22 | C01155 | | 2 | M | | * | | C00543 | 1 | M | | 275 |
| 015 | 12 | | HA | 1-2 | 24-51-22 | C01550 | | 1 | M | | * | | C00543 | 1 | M | | 276-299 |
| 016 | 10 | | HA | 2-6 | 24-51-22 | C00358 | | | B2 | D | | * | C00392 | B1 | D | * | 050-099 |
| 017 | 12 | | HA | 2-3 | 24-51-22 | C00376 | | | B1 | M | | * | C00344 | B2 | D | * | 050-099 |
| 017 | 14 | | HA | 1-11 | 24-51-22 | C00388 | | | B2 | M | | * | C00344 | B2 | M | * | 150-154, 275 |
| 017 | 14 | | HA | 7-3 | 24-51-22 | C00376 | | | B1 | M | | | K02092 | B1 | N | | 155-157, 165-199, 277-299 |
| 017 | 14 | | HA | 2-3 | 24-51-22 | C00376 | | | B1 | M | | * | C00344 | B2 | M | * | 162-164, 276 |
| 018 | 12 | | HA | 2-9 | 24-51-22 | C00358 | | | C2 | D | | * | C00392 | C1 | D | * | 050-099 |
| 018 | 12 | | HA | 2-9 | 24-51-22 | C00359 | | | C2 | M | | * | C00392 | C1 | M | | 150-157, 166-199 |
| 018 | 12 | | HA | 2-9 | 24-51-22 | C00359 | | | C2 | M | | * | C00392 | C1 | D | | 162-165 |
| 018 | 12 | | HA | 2-3 | 24-51-22 | C00359 | | | C2 | M | | * | C00392 | C1 | M | | 275-299 |
| 019 | 12 | | HA | 2-3 | 24-51-22 | C00376 | | | C1 | M | | * | C00344 | C2 | D | * | 050-099 |
| 019 | 14 | | HA | 1-11 | 24-51-22 | C00388 | | | C2 | M | | * | C00344 | C2 | M | * | 150-154 |
| 019 | 14 | | HA | 7-3 | 24-51-22 | C00376 | | | C1 | M | | | K02092 | C1 | N | | 155-157, 165-199, 277-299 |
| 019 | 14 | | HA | 2-3 | 24-51-22 | C00376 | | | C1 | M | | * | C00344 | C2 | M | * | 162-164, 276 |
| 019 | 14 | | HA | 1-11 | 24-51-22 | C00388 | | | C2 | M | | * | C00344 | C2 | M | | 275 |
| 01A | 12 | | PA | 2-7 | 24-51-22 | C00358 | | | A2 | D | | * | C00344 | A2 | D | * | 050-099 |
| 01A | 12 | | PA | 2-7 | 24-51-22 | C00344 | | | A2 | M | | * | C00358 | A2 | M | * | 150 |
| 01A | 12 | | HA | 2-7 | 24-51-22 | C00344 | | | A2 | M | | * | C00358 | A2 | M | * | 151-199 |
| 01A | 12 | | HA | 1-11 | 24-51-22 | C00344 | | | A2 | M | | * | C00358 | A2 | M | * | 275-299 |
| 01B | 12 | | PA | 0-11 | 24-51-22 | C00358 | | | A2 | D | | * | C00359 | A2 | D | * | 050-099 |
| 01B | 12 | | PA | 0-11 | 24-51-22 | C00358 | | | A2 | M | | * | C00359 | A2 | M | * | 150-154, 162-165 |
| 01B | 12 | | HA | 0-11 | 24-51-22 | C00358 | | | A2 | M | | * | C00359 | A2 | M | * | 155-157, 166-199 |
| 01B | 12 | | PA | 1-2 | 24-51-22 | C00358 | | | A2 | M | | * | C00359 | A2 | M | * | 275-276 |
| 01B | 12 | | HA | 1-2 | 24-51-22 | C00358 | | | A2 | M | | * | C00359 | A2 | M | * | 277-299 |
| 01C | 12 | | PA | 1-1 | 24-51-22 | C00344 | | | B2 | D | | * | C00392 | B1 | D | * | 050-099 |
| 01C | 12 | | PA | 2-7 | 24-51-22 | C00358 | | | B2 | M | | * | C00344 | B2 | M | * | 150 |
| 01C | 12 | | HA | 2-7 | 24-51-22 | C00358 | | | B2 | M | | * | C00344 | B2 | M | * | 151-199 |
| 01C | 12 | | HA | 1-11 | 24-51-22 | C00358 | | | B2 | M | | * | C00344 | B2 | M | * | 275-299 |
| 01D | 12 | | PA | 0-11 | 24-51-22 | C00358 | | | B2 | D | | * | C00359 | B2 | D | * | 050-099 |
| 01D | 12 | | PA | 0-11 | 24-51-22 | C00358 | | | B2 | M | | * | C00359 | B2 | D | * | 150-154, 162-165 |
| 01D | 12 | | HA | 0-11 | 24-51-22 | C00358 | | | B2 | M | | * | C00359 | B2 | M | * | 155-157, 166-199 |
| 01D | 12 | | PA | 1-2 | 24-51-22 | C00358 | | | B2 | M | | * | C00359 | B2 | M | * | 275-276 |
| 01D | 12 | | HA | 1-2 | 24-51-22 | C00358 | | | B2 | M | | * | C00359 | B2 | M | * | 277-299 |

WIRE LIST

D280T132

91-21-11

Section W1040

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1046 | 286T1046 | | | P37-R1-POWER DISTRIBUTION (continued) | | | | | | | | | | | | |
| 01E | 12 | | PA | 2-7 | 24-51-22 | C00358 | C2 | M | * | C00344 | C2 | M | * | 150 | | |
| 01E | 12 | | HA | 2-7 | 24-51-22 | C00358 | C2 | M | * | C00344 | C2 | M | * | 151-199 | | |
| 01E | 12 | | HA | 1-11 | 24-51-22 | C00358 | C2 | M | * | C00344 | C2 | M | * | 275 | | |
| 01E | 12 | | HA | 1-11 | 24-51-22 | C00358 | C2 | M | * | C00344 | C2 | M | * | 276-299 | | |
| 01F | 12 | | PA | 0-11 | 24-51-22 | C00358 | C2 | D | * | C00359 | C2 | D | * | 050-099 | | |
| 01F | 12 | | PA | 0-11 | 24-51-22 | C00358 | C2 | M | * | C00359 | C2 | M | * | 150-154, 162-165 | | |
| 01F | 12 | | HA | 0-11 | 24-51-22 | C00358 | C2 | M | * | C00359 | C2 | M | * | 155-157, 166-199 | | |
| 01F | 12 | | PA | 1-2 | 24-51-22 | C00358 | C2 | M | * | C00359 | C2 | M | * | 275-276 | | |
| 01F | 12 | | HA | 1-2 | 24-51-22 | C00358 | C2 | M | * | C00359 | C2 | M | * | 277-299 | | |
| 01G | 12 | | PA | 2-9 | 24-51-22 | C00392 | B1 | D | * | C00359 | B2 | D | * | 150-154, 162-165 | | |
| 01G | 12 | | HA | 2-9 | 24-51-22 | C00392 | B1 | M | * | C00359 | B2 | M | * | 155-157, 166-199 | | |
| 01G | 12 | | PA | 2-3 | 24-51-22 | C00359 | B2 | M | * | C00392 | B1 | D | * | 275-276 | | |
| 01G | 12 | | HA | 2-3 | 24-51-22 | C00359 | B2 | M | * | C00392 | B1 | M | * | 277-299 | | |
| 021 | 10 | | HA | 9-5 | 24-51-23 | TB5132 | 4 | N | | C01282 | 2 | M | | 050-099, 277-299 | | |
| 021 | 12 | | HA | 9-11 | 24-51-23 | C01282 | 2 | N1 | | TB5132 | 4 | E | | 150-154, 162-165 | | |
| 021 | 12 | | HA | 9-11 | 24-51-23 | C01282 | 2 | M | | TB5132 | 4 | N | | 155-157, 166-199 | | |
| 021 | 10 | | PA | 9-5 | 24-51-23 | TB5132 | 4 | E | | C01282 | 2 | D | | 275-276 | | |
| 024 | 12 | | HA | 10-0 | 24-51-23 | TB5132 | 5 | N | | C00700 | 1 | M | * | ALL | | |
| 025 | 14 | | HA | 1-3 | 24-51-23 | C00700 | 1 | M | * | C01366 | 1 | M | * | ALL | | |
| 028 | 12 | | HA | 10-1 | 24-51-23 | TB5132 | 6 | N | | C00699 | 1 | M | * | ALL | | |
| 030 | 14 | | HA | 4-6 | 24-51-22 | TB5132 | 2 | N | | L00573 | 1 | L | | ALL | | |
| 031 | 14 | | HA | 3-4 | 24-51-22 | L00573 | 2 | L | | GDX0010 | A.. | P | | ALL | | |
| 032 | 14 | | HA | 4-6 | 24-51-23 | TB5132 | 4 | N | *1 | L00574 | 1 | L | | ALL | | |
| 033 | 14 | | HA | 3-4 | 24-51-23 | L00574 | 2 | L | | GDX0010 | A.. | P | | ALL | | |
| 034 | 12 | | HA | 2-9 | 24-51-22 | C01149 | 2 | M | | C00344 | B2 | M | * | 275 | | |
| 035 | 10 | | HA | 0-10 | 24-51-22 | C01151 | 2 | M | * | C01166 | 1 | M | * | 275 | | |
| 036 | 12 | | HA | 1-0 | 24-51-22 | C01151 | 2 | M | * | C01155 | 2 | M | * | 275 | | |
| 037 | 10 | | HA | 9-1 | 24-51-22 | TB5132 | 3 | N | | C01156 | 2 | M | * | 275 | | |
| 038 | 12 | | HA | 1-0 | 24-51-22 | C01156 | 2 | M | * | C01158 | 2 | M | * | 275 | | |
| 039 | 12 | | HA | 1-1 | 24-51-22 | C01158 | 2 | M | * | C01157 | 2 | M | * | 275 | | |
| 044 | 12 | | HA | 1-11 | 24-51-23 | C01373 | 1 | M | * | C01275 | 2 | M | | 050-099 | | |
| 044 | 12 | | PA | 1-2 | 24-51-23 | C01373 | 1 | N1 | * | C00699 | 1 | M | * | 150-154, 162-165 | | |
| 044 | 12 | | HA | 1-2 | 24-51-23 | C01373 | 1 | M | * | C00699 | 1 | M | * | 155-157, 166-199 | | |
| 045 | 12 | | HA | 1-2 | 24-51-23 | C00699 | 1 | M | * | C01373 | 1 | M | * | 050-099 | | |
| 045 | 12 | | PA | 1-11 | 24-51-23 | C01373 | 1 | N1 | * | C01275 | 2 | D | | 150-154, 162-165 | | |
| 045 | 12 | | HA | 1-11 | 24-51-23 | C01373 | 1 | M | * | C01275 | 2 | M | | 155-157, 166-199 | | |
| 045 | 12 | | PA | 2-2 | 24-51-23 | C00699 | 1 | M | * | C01275 | 2 | D | | 275-276 | | |
| 045 | 12 | | HA | 2-2 | 24-51-23 | C00699 | 1 | M | * | C01275 | 2 | M | | 277-299 | | |
| 048 | 14 | | HA | 2-9 | 24-51-22 | C01126 | 2 | M | * | C00555 | 1 | M | | 050-099, 155-199 | | |

WIRE LIST
D280T132

91-21-11
Section W1040
Page 8
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|--------|--------|-------------|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1046 | 286T1046 | | | P37-R1-POWER DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 048 | 14 | | HA | 9-10 | 24-51-22 | TB5132 | | 1 | N | | | | C00555 | 1 | M | | 150-154 |
| 048 | 12 | | HA | 10-4 | 24-51-22 | TB5132 | | 1 | N | | | | C01551 | 2 | M | | 275 |
| 048 | 14 | | HA | 3-2 | 24-51-22 | C01126 | | 2 | M | * | | | C01551 | 2 | M | | 276-299 |
| 049 | 12 | | HA | 7-0 | 24-51-22 | K02092 | | C3 | N | | | | C00549 | 1 | M | | 050-099, 155-199 |
| 049 | 12 | | HA | 10-0 | 24-51-22 | TB5132 | | 3 | N | | | | C00549 | 1 | M | | 150-154 |
| 049 | 12 | | HA | 9-11 | 24-51-22 | TB5132 | | 3 | N | | | | C01550 | 1 | M | | 275 |
| 049 | 12 | | HA | 6-11 | 24-51-22 | K02092 | | C3 | N | | | | C01550 | 1 | M | * | 276-299 |
| 04A | 12 | | HA | 10-2 | 24-51-22 | TB5132 | | 2 | N | | | | C01553 | 2 | M | | 275 |
| 04A | 12 | | HA | 7-1 | 24-51-22 | K02092 | | B3 | N | | | | C01553 | 2 | M | | 276-299 |
| 054 | 10 | | HA | 9-5 | 24-51-22 | TB5132 | | 1 | N | | | | C01166 | 1 | M | * | 275 |
| 060 | 12 | | HA | 6-1 | 24-51-22 | K02092 | | A3 | N | | | | C01126 | 2 | M | * | 050-099, 155-199, 276-299 |
| 061 | 12 | | HA | 3-10 | 24-51-22 | K02092 | | A2 | N | | | | TB5132 | 1 | N | | 050-099 |
| 061 | 12 | | HA | 3-10 | 24-51-22 | TB5132 | | 1 | N | | | | K02092 | A2 | N | | 155-199, 276-299 |
| 062 | 12 | | HA | 3-10 | 24-51-22 | K02092 | | B2 | N | | | | TB5132 | 2 | N | | 050-099 |
| 062 | 12 | | HA | 3-10 | 24-51-22 | TB5132 | | 2 | N | | | | K02092 | B2 | N | | 155-199, 276-299 |
| 063 | 12 | | HA | 3-10 | 24-51-22 | K02092 | | C2 | N | | | | TB5132 | 3 | N | | 050-099 |
| 063 | 12 | | HA | 3-10 | 24-51-22 | TB5132 | | 3 | N | | | | K02092 | C2 | N | | 155-199, 276-299 |
| 064 | 12 | | HA | 1-3 | 24-51-22 | C00388 | | A2 | M | * | | | C00376 | A1 | M | * | 050-099, 162-164, 276 |
| 064 | 12 | | HA | 1-11 | 24-51-22 | C00388 | | A2 | M | * | | | C00344 | A2 | M | * | 155-157, 165-199, 277-299 |
| 065 | 12 | | HA | 1-3 | 24-51-22 | C00388 | | B2 | M | * | | | C00376 | B1 | M | * | 050-099, 162-164, 276 |
| 065 | 12 | | HA | 1-11 | 24-51-22 | C00388 | | B2 | M | * | | | C00344 | B2 | M | * | 155-157, 165-199, 277-299 |
| 066 | 12 | | PA | 1-3 | 24-51-22 | C00388 | | C2 | M | * | | | C00376 | C1 | M | * | 050-099 |
| 066 | 12 | | HA | 1-11 | 24-51-22 | C00388 | | C2 | M | * | | | C00344 | C2 | M | * | 155-157, 165-199, 277-299 |
| 066 | 12 | | HA | 1-3 | 24-51-22 | C00388 | | C2 | M | * | | | C00376 | C1 | M | * | 162-164, 276 |
| 067 | 12 | | PA | 1-1 | 24-51-22 | C00344 | | C2 | D | * | | | C00392 | C1 | D | * | 050-099 |
| 072 | 12 | | PA | 1-2 | 24-51-23 | C00404 | | C1 | D | * | | | C00405 | C2 | D | * | 050-099, 162-165 |
| 072 | 12 | | PA | 1-2 | 24-51-23 | C00404 | | C1 | D | * | | | C00407 | C2 | D | * | 150, 152-157 |
| 072 | 12 | | HA | 1-2 | 24-51-23 | C00404 | | C1 | M | * | | | C00405 | C2 | M | * | 166-199 |
| 073 | 12 | | PA | 1-2 | 24-51-23 | C00404 | | B1 | D | * | | | C00405 | B2 | D | * | 050-099, 162-165 |
| 073 | 12 | | PA | 1-2 | 24-51-23 | C00404 | | B1 | D | * | | | C00407 | B2 | D | * | 150, 152-157 |
| 073 | 12 | | HA | 1-2 | 24-51-23 | C00404 | | B1 | M | * | | | C00405 | B2 | M | * | 166-199 |
| 074 | 12 | | PA | 1-2 | 24-51-23 | C00404 | | A1 | D | * | | | C00405 | A2 | D | * | 050-099, 162-165 |
| 074 | 12 | | PA | 1-2 | 24-51-23 | C00404 | | A1 | D | * | | | C00407 | A2 | D | * | 150, 152-157 |
| 074 | 12 | | HA | 1-2 | 24-51-23 | C00404 | | A1 | M | * | | | C00405 | A2 | M | * | 166-199 |
| 075 | 12 | | PA | 1-2 | 24-51-23 | C00404 | | C1 | D | * | | | C00402 | C1 | D | | 050-099, 162-165 |

WIRE LIST

D280T132

91-21-11

Section W1040

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1046 | 286T1046 | | | P37-R1-POWER DISTRIBUTION (continued) | | | | | | | | | | | | |
| 075 | 12 | | HA | 1-2 | 24-51-23 | C00404 | C1 | M | * | C00402 | C1 | M | | 166-199 | | |
| 076 | 12 | | PA | 1-2 | 24-51-23 | C00404 | B1 | D | * | C00402 | B1 | D | | 050-099, 162-165 | | |
| 076 | 12 | | HA | 1-2 | 24-51-23 | C00404 | B1 | M | * | C00402 | B1 | M | | 166-199 | | |
| 077 | 12 | | PA | 1-2 | 24-51-23 | C00404 | A1 | D | * | C00402 | A1 | D | | 050-099, 162-165 | | |
| 077 | 12 | | HA | 1-2 | 24-51-23 | C00404 | A1 | M | * | C00402 | A1 | M | | 166-199 | | |
| 078 | 12 | | PA | 1-2 | 24-51-23 | C00405 | A2 | D | * | C00407 | A2 | D | * | 050-099, 162-165 | | |
| 078 | 12 | | HA | 1-2 | 24-51-23 | C00405 | A2 | M | * | C00407 | A2 | M | * | 166-199 | | |
| 079 | 12 | | PA | 1-2 | 24-51-23 | C00405 | B2 | D | * | C00407 | B2 | D | * | 050-099, 162-165 | | |
| 079 | 12 | | HA | 1-2 | 24-51-23 | C00405 | B2 | M | * | C00407 | B2 | M | * | 166-199 | | |
| 080 | 12 | | PA | 1-2 | 24-51-23 | C00405 | C2 | D | * | C00407 | C2 | D | * | 050-099, 162-165 | | |
| 080 | 12 | | HA | 1-2 | 24-51-23 | C00405 | C2 | M | * | C00407 | C2 | M | * | 166-199 | | |
| 081 | 12 | | PA | 2-5 | 24-51-23 | C00407 | A2 | D | * | C00337 | A2 | D | * | 050-099, 150, 152-165 | | |
| 081 | 12 | | HA | 2-5 | 24-51-23 | C00407 | A2 | M | * | C00337 | A2 | M | * | 166-199 | | |
| 082 | 12 | | PA | 2-5 | 24-51-23 | C00407 | B2 | D | * | C00337 | B2 | D | * | 050-099, 150, 152-165 | | |
| 082 | 12 | | HA | 2-5 | 24-51-23 | C00407 | B2 | M | * | C00337 | B2 | M | * | 166-199 | | |
| 083 | 12 | | PA | 2-5 | 24-51-23 | C00407 | C2 | D | * | C00337 | C2 | D | * | 050-099, 150, 152-165 | | |
| 083 | 12 | | HA | 2-5 | 24-51-23 | C00407 | C2 | M | * | C00337 | C2 | M | * | 166-199 | | |
| 084 | 08 | | PA | 8-7 | 24-54-21 | TB5132 | 7 | E | | C00665 | 2 | D | * | 050-099, 162-165 | | |
| 084 | 08 | | HA | 8-7 | 24-54-21 | TB5132 | 7 | N | | C00665 | 2 | M | * | 166-199 | | |
| 084 | 08 | | HA | 8-7 | 24-54-21 | TB5132 | 7 | N | | C00665 | 2 | M | | 277-299 | | |
| 085 | 08 | | PA | 2-0 | 24-54-21 | C00665 | 2 | D | * | C00923 | 1 | D | * | 050-099, 162-165 | | |
| 085 | 08 | | PA | 2-0 | 24-54-21 | C00665 | 2 | D | | C00923 | 1 | D | * | 150, 152-157 | | |
| 085 | 08 | | HA | 2-0 | 24-54-21 | C00665 | 2 | M | * | C00923 | 1 | M | * | 166-199 | | |
| 086 | 08 | | PA | 3-0 | 24-54-21 | C00923 | 1 | D | * | C00920 | 1 | D | | 050-099, 150, 152-165 | | |
| 086 | 08 | | HA | 3-0 | 24-54-21 | C00923 | 1 | M | * | C00920 | 1 | M | | 166-199 | | |
| 130 | 10 | | HA | 12-0 | 24-51-23 | C01195 | A1 | M | | C00337 | A2 | M | | 275-299 | | |
| 131 | 10 | | HA | 12-0 | 24-51-23 | C01195 | B1 | M | | C00337 | B2 | M | | 275-299 | | |
| 132 | 10 | | HA | 12-0 | 24-51-23 | C01195 | C1 | M | | C00337 | C2 | M | | 275-299 | | |
| 900 | 20 | | PA | 5-0 | 23-32-21 | D04340J | 10 | | | C09002 | 1 | D | | 150, 152-156, 162-199 | | |
| 900 | 20 | | PA | 5-0 | 23-32-21 | D04340J | 10 | | | C09002 | D4 | D | | 157 | | |
| 901 | 20 | | PA | 5-0 | 23-32-21 | D04340J | 8 | | | C09000 | 1 | D | | 150, 152-156, 162-199 | | |
| 901 | 20 | | PA | 5-0 | 23-32-21 | D04340J | 8 | | | C09000 | D5 | D | | 157 | | |
| 902 | 12 | | PA | 5-0 | 24-51-22 | C00550 | 1 | D | | C09002 | 1 | D | | 150, 152-199 | | |
| 903 | 12 | | PA | 5-0 | 24-54-21 | C09000 | 2 | D | | C00918 | 1 | D | | 162-199 | | |
| W1047 | 286T1047 | | | COAX-SATCOM,M1783 HPA TO AP1101 (SPLITTER) | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-11 | D06179J | = C1 | | | D02653A | = C71 | | | 156-157, 166-199, 277-299 | | |

WIRE LIST
D280T132

91-21-11
Section W1040
Page 10
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|--------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1047 | 286T1047 | | | COAX-SATCOM,M1783 HPA TO AP1101 (SPLITTER) (continued) | | | | | | | | | | | | |
| 01CX | | 78 | A | 1-2 | 23-25-11 | D06179J | = A1 | | | D02653A | 71 | | | 156-157, 166-199, 277-299 | | |
| W1048 | 286T1048 | | | P49-A1-APU BATT BUS DISTRIBUTION | | | | | | | | | | | | |
| 003 | *1 | | HA | 3-3 | 24-31-41 | D00300 | + Q | | | K00117 | A2 | R | | ALL | | |
| 004 | 08 | | HA | 0-10 | 24-31-41 | M00228 | =B F | | | GD03076 | D.. | E | | ALL | | |
| 005 | 08 | | HA | 3-3 | 24-31-41 | M00207 | + H | | | C00868 | 1 | F | *1 | ALL | | |
| 006 | *1 | | HA | 2-3 | 24-31-41 | C00868 | 2 FP | | | K00117 | A2 | R | | 050-099, 155-199, 276-299 | | |
| 006 | *1 | | HA | 2-3 | 24-31-41 | C00868 | 2 F | | | K00117 | A2 | R | | 150-154, 275 | | |
| 007 | *1 | | HA | 3-0 | 24-31-41 | GD03072 | D.. IT | | | D00300 | - | Q | | 050-099, 150-199 | | |
| 007 | *1 | | HA | 3-0 | 24-31-41 | GD03072 | D.. R | | | D00300 | - | Q | | 275-299 | | |
| 008 | 08 | | HA | 0-8 | 24-31-41 | C00869 | 1 D | | | C00868 | 1 | F | *1 | ALL | | |
| 009 | 08 | | HA | 2-4 | 24-31-41 | M00207 | - G | | | M00228 | =A | F | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W1040

Page 11 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1050 | 286T1050 | | | P49-A1-APU BATT BUS DISTRIBUTION | | | | | | | | | | | | |
| 001 | 20 | | PA | | 6-0 | 24-32-41 | D01076 | | A | | D01000 | | A1 | | 275-299 | |
| 002 | 20 | | PA | | 6-0 | 24-32-41 | D01076 | | B | | D01000 | | B1 | | 275-299 | |
| 003 | 20 | | PA | | 6-0 | 24-32-41 | D01076 | | C | | D01000 | | C1 | | 275-299 | |
| 004 | 20 | | PA | | 6-0 | 24-32-41 | D01076 | | G | | D01000 | | D1 | | 275-299 | |
| 005 | 20 | | PA | | 6-0 | 24-32-41 | D01076 | | H | | GDX0001 | | A.. | 2 | 275-299 | |
| 006 | 08 | | PA | | 4-0 | 24-32-41 | D01076 | | F | | K00618 | | C2 | E | 275-299 | |
| 007 | 08 | | PA | | 4-0 | 24-32-41 | D01076 | | E | | K00618 | | B2 | E | 275-299 | |
| 008 | 08 | | PA | | 4-0 | 24-32-41 | D01076 | | D | | K00618 | | A2 | E | 275-299 | |
| 009 | 20 | | PA | | 7-0 | 24-32-41 | D01076 | | I | | TB0300Y | | C017 | BJ | 275-299 | |
| 010 | 20 | | PA | | 5-0 | 24-32-41 | D01000 | | A2 | | C00089 | | A2 | D | 275-299 | |
| 011 | 20 | | PA | | 5-0 | 24-32-41 | D01000 | | B2 | | C00089 | | B2 | D | 275-299 | |
| 012 | 20 | | PA | | 5-0 | 24-32-41 | D01000 | | C2 | | C00089 | | C2 | D | 275-299 | |
| 013 | 20 | | PA | | 3-0 | 24-32-41 | D01000 | | X1 | | TB0300Y | | A015 | BJ | 275-299 | |
| 014 | 14 | | PA | | 3-0 | 24-31-41 | C00869 | | 2 | D | C01383 | | 1 | D | * | 050-099 |
| 014 | 14 | | PA | | 2-0 | 24-31-41 | C00869 | | 2 | D | C01383 | | 1 | D | * | 150-199, 275-299 |
| 016 | 14 | | PA | | 3-0 | 24-31-41 | C01383 | | 1 | D | C01385 | * | 1 | D | * | ALL |
| 017 | 14 | | PA | | 2-0 | 24-31-41 | C00820 | | 1 | D | C01385 | * | 1 | D | * | 050-099 |
| 017 | 14 | | PA | | 3-0 | 24-31-41 | C00820 | | 1 | D | C01385 | * | 1 | D | * | 150-199, 275-299 |
| 018 | 16 | | PA | | 7-0 | 49-15-11 | D00326 | | B3 | | D06396J | | 21 | | 050-099 | |
| 018 | 16 | | PA | | 4-0 | 49-15-11 | D00326 | | B3 | | D06396J | | 21 | | 150-199, 275-299 | |
| 019 | 16 | | PA | | 3-0 | 49-15-11 | D00326 | | B1 | | TB0300G | | 10 | 2 | 050-099, 150-199 | |
| 019 | 16 | | PA | | 4-0 | 49-15-11 | D00326 | | B1 | | TB0300G | | 10 | 2 | 275-299 | |
| 020 | 22 | | PA | | 4-0 | 49-15-11 | D00326 | | A3 | | D06396J | | 24 | | ALL | |
| 021 | 24 | | PK | | 4-0 | 49-15-11 | D00326 | | A1 | | D06396J | | 26 | | ALL | |
| 022 | 24 | | PK | | 3-0 | 49-15-11 | D00326 | | A2 | | TB0300Y | | A017 | BJ | ALL | |
| 023 | 16 | | PA | | 5-0 | 49-15-11 | TB0300G | | 22 | 2 | C01385 | | 2 | D | ALL | |
| 024 | 22 | | PA | | 3-0 | 49-41-11 | TB0300Y | | C016 | BJ | D00998 | | A2 | | 275-299 | |
| 025 | 20 | | PA | | 3-0 | 24-32-41 | D01074 | | X1 | | TB0300Y | | A015 | BJ | 275-299 | |
| 026 | 24 | | PK | | 3-0 | 24-31-41 | D01834 | | B2 | | TB0300Y | | C009 | BJ | ALL | |
| 027 | 20 | | PA | | 2-0 | 24-31-41 | D01834 | | B1 | | GDX0001 | | D.. | 2 | ALL | |
| 028 | 22 | | PA | | 6-0 | 49-61-11 | C00020 | | 2 | D | TB0300Z | | 19 | BJ | ALL | |
| 029 | 20 | | PA | | 5-0 | 49-41-11 | K00117 | | X2 | E | GDX0001 | | D.. | 2 | 050-099 | |
| 029 | 20 | | PA | | 6-0 | 49-41-11 | K00117 | | X2 | E | GDX0001 | | D.. | 2 | 150-199, 275-299 | |
| 030 | 22 | | PA | | 3-0 | 49-41-11 | K00117 | | X1 | E | D01834 | | A1 | | 050-099 | |
| 030 | 22 | | PA | | 5-0 | 49-41-11 | K00117 | | X1 | E | D01834 | | A1 | | 150-199 | |
| 030 | 22 | | PA | | 4-0 | 49-41-11 | K00117 | | X1 | E | D00998 | | A3 | | 275-299 | |
| 031 | 22 | | PA | | 3-0 | 49-41-11 | TB0300Z | | 19 | BJ | D01834 | | A2 | | ALL | |
| 032 | 22 | | PA | | 3-0 | 49-41-11 | TB0300Z | | 19 | BJ | D01834 | | X1 | | ALL | |
| 033 | 24 | | PK | | 4-0 | 49-41-11 | D06396J | | 29 | | D01834 | | X2 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1050

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1050 | 286T1050 | | | P49-A1-APU BATT BUS DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 034 | 22 | | PA | 4-0 | 49-61-11 | D06396J | | 31 | | | | | D00326 | X2 | | | ALL |
| 035 | 22 | | PA | 3-0 | 49-61-11 | TB0300Z | | 19 | BJ | | | | D00326 | X1 | | | ALL |
| 036 | 16 | | PA | 3-0 | 49-61-11 | R00012 | | A | \$ | | | | TB0294F | A001 | 2 | | ALL |
| 037 | 16 | | PA | 6-0 | 49-61-11 | TB0300G | | 21 | 2 | | | | C00020 | 1 | D | | ALL |
| 038 | 16 | | PA | 5-0 | 49-61-11 | D06396J | | 30 | FL | | | | TB0300G | 21 | 2 | | ALL |
| 039 | 22 | | PA | 5-0 | 49-61-11 | D06396J | | 32 | | | | | TB0300Z | 19 | BJ | | ALL |
| 041 | 16 | | PA | 5-0 | 49-61-11 | TB0300G | | 21 | 2 | | | | R00011 | C | E | | ALL |
| 042 | 16 | | PA | 5-0 | 49-61-11 | TB0300G | | 21 | 2 | | | | R00012 | C | E | | ALL |
| 043 | 16 | | PA | 3-0 | 49-15-11 | TB0300G | | 22 | 2 | | | | D00326 | B2 | | | ALL |
| 044 | 22 | | PA | 4-0 | 49-15-11 | D06396J | | 28 | | | | | D01264 | 7 | | | ALL |
| 045 | 16 | | PA | 3-0 | 49-61-11 | TB0294F | | A002 | 2 | | | | R00011 | A | \$ | | 050-099 |
| 045 | 16 | | PA | 2-0 | 49-61-11 | R00011 | | A | \$ | | | | TB0294F | A002 | 2 | | 150-199, 275-299 |
| 046 | 24 | | PK | 3-0 | 24-34-11 | D06396J | | 15 | | | | | M00228 | =D | D | | ALL |
| 047 | 24 | | PK | 3-0 | 24-34-11 | D06396J | | 16 | | | | | M00228 | =C | D | | ALL |
| 048 | 24 | | PK | 4-0 | 49-15-11 | D01264 | | 1 | | | | | D06396J | 27 | | | ALL |
| 050 | 22 | | PA | 3-0 | 49-15-11 | D01264 | | 3 | | | | | TB0300G | 22 | 2 | | ALL |
| 051 | 24 | | PK | 3-0 | 49-15-11 | D01264 | | 6 | | | | | TB0300Y | A017 | BJ | | ALL |
| 052 | 24 | | PK | 5-0 | 49-15-11 | D06396J | | 22 | | | | | TB0300Y | A017 | BJ | | ALL |
| 053 | 20 | | PA | 2-0 | 24-32-41 | D01074 | | X2 | | | | | GDX0001 | A.. | 2 | | 275-299 |
| 054 | 20 | | PA | 4-0 | 24-32-41 | D01074 | | A2 | | | | | D06396J | 10 | | | 275-299 |
| 055 | 20 | | PA | 4-0 | 24-32-41 | D01074 | | A1 | | | | | TB0300Y | C015 | BJ | | 275-299 |
| 056 | 20 | | PA | 1-8 | 24-32-41 | D01008 | | A2 | | | | | TB0300Y | C015 | BJ | | 275-299 |
| 057 | 20 | | PA | 1-8 | 24-32-41 | D01008 | | X1 | | | | | TB0300Y | C016 | BJ | | 275-299 |
| 058 | 20 | | PA | 2-0 | 24-32-41 | D00998 | | X1 | | | | | D01008 | A3 | | | 275-299 |
| 059 | 20 | | PA | 2-0 | 24-32-41 | D00998 | | X2 | | | | | GDX0001 | D.. | 2 | | 275-299 |
| 060 | 20 | | PA | 4-0 | 24-32-41 | D00998 | | A1 | | | | | K00618 | X1 | C | | 275-299 |
| 061 | 20 | | PA | 4-0 | 24-32-41 | GDX0001 | | D.. | 2 | | | | K00618 | X2 | C | | 275-299 |
| 064 | 24 | | PK | 5-0 | 31-31-22 | TB0300G | | 10 | 2 | | | | D06396J | 1 | | | ALL |
| 065 | 20 | | PA | 4-0 | 24-32-41 | TB0300Y | | A016 | BJ | | | | K00618 | 11 | C | | 275-299 |
| 066 | 20 | | PA | 4-0 | 24-32-41 | GDX0001 | | A.. | 2 | | | | K00618 | 12 | C | | 275-299 |
| 067 | 20 | | PA | 3-0 | 24-32-41 | D01000 | | D2 | | | | | TB0300Y | A016 | BJ | | 275-299 |
| 068 | 20 | | PA | 3-0 | 24-32-41 | D01000 | | X2 | | | | | TB0300Y | A016 | BJ | | 275-299 |
| 069 | 08 | | PA | 4-0 | 24-32-41 | C00089 | | A1 | D | | | | K00618 | A1 | E | | 275-299 |
| 070 | 08 | | PA | 4-0 | 24-32-41 | C00089 | | B1 | D | | | | K00618 | B1 | E | | 275-299 |
| 071 | 08 | | PA | 4-0 | 24-32-41 | C00089 | | C1 | D | | | | K00618 | C1 | E | | 275-299 |
| 073 | 20 | | PA | 5-0 | 24-32-41 | TB0300Y | | A015 | BJ | | | | C00089 | C2 | D | | 275-299 |
| 079 | 24 | | PK | 4-0 | 24-34-11 | C00821 | | 2 | D | | | | D06396J | 17 | | | ALL |
| 080 | 14 | | PA | 2-5 | 24-31-41 | C00821 | | 1 | D | | | | C00820 | 1 | D | * | ALL |
| 081 | 16 | | PA | 3-0 | 49-61-11 | C01383 | | 2 | D | | | | TB0294F | A001 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1050

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1050 | 286T1050 | | | P49-A1-APU BATT BUS DISTRIBUTION (continued) | | | | | | | | | | | |
| 082 | 16 | | PA | | 3-0 | 49-61-11 | D06396J | 33 | FL | | TB0294F | A002 | 2 | | ALL |
| 092 | 24 | | PK | | 5-0 | 24-51-71 | D06396J | 25 | | | TB0300X | B011 | BJ | | ALL |
| 093 | 24 | | PK | | 5-0 | 24-51-71 | D06396J | 20 | | | TB0300X | C011 | BJ | | ALL |
| 094 | 24 | | PK | | 3-0 | 49-15-11 | D01264 | 2 | | | D06396J | 9 | | | ALL |
| 095 | 20 | | PA | | 2-0 | 49-15-11 | D01264 | 5 | | | GD0001 | D.. | 2 | | ALL |
| 098 | 24 | | PK | | 5-0 | 38-15-11 | D06396J | 34 | | | TB0300Y | A005 | BJ | | ALL |
| 099 | 22 | | PA | | 4-0 | 49-15-11 | D06396J | 8 | | | D01264 | 8 | | | ALL |
| 101 | 20 | | PA | | 1-8 | 24-32-41 | D01008 | B1 | | | TB0300Y | C017 | BJ | | 275-299 |
| 102 | 20 | | PA | | 1-8 | 24-32-41 | D01008 | X2 | | | TB0300Y | C017 | BJ | | 275-299 |
| 104 | 20 | | PA | | 1-2 | 24-32-41 | D01008 | B2 | | | GD0001 | D.. | 2 | | 275-299 |
| 105 | 22 | | PA | | 2-0 | 49-41-11 | TB0300Y | C016 | BJ | | D01834 | A1 | | | 275-299 |
| 119 | 16 | | PA | | 5-0 | 49-15-11 | D06396J | 23 | | | TB0300G | 10 | 2 | | 050-099, 150-199 |
| 119 | 16 | | PA | | 5-0 | 49-15-11 | TB0300G | 10 | 2 | | D06396J | 23 | | | 275-299 |
| 129 | 24 | | PK | | 5-0 | 31-31-22 | TB0300F | A014 | 2 | | D06396J | 3 | | | ALL |
| 130 | 24 | | PK | | 5-0 | 31-31-22 | TB0300F | C014 | 2 | | D06396J | 2 | | | ALL |
| PA1 | | | | | 0-0 | 99-99-99 | D01000 | G1 | | | D01000 | G3 | | | 275-299 |
| W1051 | 286T1051 | | | E1-3 SHELF,L ILS LOC COAX | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-31-11 | D00429C | = C1 | | | D04045J | = C1 | | | ALL |
| 01CX | | | | 66 A | 0-5 | 34-31-11 | D00429C | 1 | | | D04045J | = A1 | | | ALL |
| W1052 | 286T1052 | | | P7 INTEG PNL LEFT SIDE | | | | | | | | | | | |
| 001 | 24 | | PK | | 7-0 | 33-14-11 | D05016P | 3 | | | R00505 | 1 | C | | ALL |
| 002 | 24 | | PK | | 7-0 | 33-14-11 | D05016P | 4 | | | R00505 | 2 | C | | ALL |
| 003 | 24 | | PK | | 6-0 | 33-14-21 | D05014P | 10 | | | R00503 | 1 | C | | ALL |
| 004 | 20 | | PA | | 5-0 | 33-14-21 | GD04478 | A.. | 2 | | L00028 | = G | C | | ALL |
| 005 | 20 | | PA | | 4-0 | 31-51-21 | D05014P | 9 | | | S00507 | 2 | 1A | | ALL |
| 006 | 24 | | PK | | 4-0 | 31-51-21 | D05014P | 8 | | | S00507 | 3 | 1A | | ALL |
| 009 | 22 | | PA | | 4-0 | 33-16-16 | D05014P | 12 | | | S00507 | 18 | 1A | | ALL |
| 010 | 22 | | PA | | 4-0 | 33-16-16 | D05014P | 13 | | | S00507 | 17 | 1A | | ALL |
| 012 | 24 | | PK | | 4-0 | 31-51-21 | D05014P | 7 | | | S00507 | 15 | 1A | | ALL |
| 013 | 22 | | PQ | B | 4-0 | 33-16-16 | D04982P | 21 | | | S00507 | 13 | 1A | | ALL |
| 013Z | | | | B | 0-0 | 33-16-16 | D04982P | DED | | | S00507 | DED | | | ALL |
| 014 | 22 | | PQ | C | 4-0 | 33-16-16 | D04982P | 22 | | | S00507 | 14 | 1A | | ALL |
| 014Z | | | | C | 0-0 | 33-16-16 | D04982P | DED | | | S00507 | DED | | | ALL |
| 015 | 20 | | PA | | 5-0 | 33-11-11 | GD04478 | S.. | 2 | | D00584 | 6 | | | ALL |
| 016 | 20 | | UA | | 7-0 | 33-11-11 | R00507 | | | FA | GD04478 | S.. | 2 | | ALL |
| 018 | 24 | | PK | | 4-0 | 34-22-15 | D04867P | 3 | | | TB0178N | C001 | 1B | | ALL |
| 019 | 24 | | PK | | 4-0 | 34-22-15 | D04867P | 4 | | | TB0178N | D001 | 1B | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1050
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1052 | 286T1052 | | | P7 INTEG PNL LEFT SIDE (continued) | | | | | | | | | | | | |
| 020 | 24 | | PK | | 4-0 | 34-22-15 | D04867P | | 5 | | | TB0178N | E001 | 1B | | ALL |
| 021 | 20 | | PA | | 6-0 | 33-13-17 | D04982P | | 26 | | | L00482 | =P | B | | ALL |
| 022 | 20 | | PA | | 7-0 | 33-13-17 | GD04478 | A.. | 2 | | | L00482 | =G | G | | ALL |
| 023 | 20 | | PA | | 4-0 | 33-11-11 | GD04478 | S.. | 2 | | | D00586 | | 5 | | ALL |
| 024 | 22 | | PA | | 6-0 | 33-11-11 | D04982P | | 1 | | | R00507 | =A | \$ | | ALL |
| 025 | 22 | | PA | | 6-0 | 33-11-11 | D04982P | | 2 | | | R00507 | =B | \$ | | ALL |
| 027 | 24 | | PK | | 4-0 | 31-41-16 | D05014P | | 5 | | | S00507 | | 6 | 1A | ALL |
| 028 | 24 | | PK | | 4-0 | 31-41-16 | D05014P | | 6 | | | S00507 | | 5 | 1A | ALL |
| 029 | 24 | | PK | | 4-0 | 31-41-16 | D05014P | | 4 | | | S00507 | | 16 | 1A | ALL |
| 201B | 24 | | PL | AA | 4-0 | 34-22-15 | D04867P | | 2 | | | TB0178N | B001 | 1B | | ALL |
| 201R | 24 | | PL | AA | 0-0 | 34-22-15 | D04867P | | 1 | | | TB0178N | A001 | 1B | | ALL |
| 203B | 24 | | PL | AC | 5-0 | 33-11-11 | D04982P | | 4 | | | D00584 | | 4 | | ALL |
| 203R | 24 | | PL | AC | 0-0 | 33-11-11 | D04982P | | 5 | | | D00584 | | 5 | | ALL |
| 204B | 24 | | PL | AD | 5-0 | 33-11-11 | D04982P | | 6 | | | D00584 | | 11 | | ALL |
| 204R | 24 | | PL | AD | 0-0 | 33-11-11 | D04982P | | 7 | | | D00584 | | 12 | | ALL |
| 205B | 24 | | PL | AE | 5-0 | 33-11-11 | D04982P | | 12 | | | D00584 | | 7 | | ALL |
| 205R | 24 | | PL | AE | 0-0 | 33-11-11 | D04982P | | 13 | | | D00584 | | 8 | | ALL |
| 206B | 24 | | PW | AF | 6-0 | 33-11-11 | D04982P | | 3 | | | R00507 | | 2 | A | ALL |
| 206R | 24 | | PW | AF | 0-0 | 33-11-11 | D04982P | | 9 | | | R00507 | | 3 | A | ALL |
| 206Z | | | | AF | 0-0 | 33-11-11 | R00507 | | | FA | | D04982P | | 8 | | ALL |
| 208B | 24 | | PL | AH | 4-0 | 33-11-11 | D04982P | | 14 | | | D00586 | | 3 | | ALL |
| 208R | 24 | | PL | AH | 0-0 | 33-11-11 | D04982P | | 15 | | | D00586 | | 4 | | ALL |
| 209B | 24 | | PL | AJ | 4-0 | 33-11-11 | D04982P | | 19 | | | D00586 | | 1 | | ALL |
| 209R | 24 | | PL | AJ | 0-0 | 33-11-11 | D04982P | | 20 | | | D00586 | | 2 | | ALL |
| 301B | 24 | | PX | BA | 7-0 | 31-25-11 | D05014P | | 2 | | | S00320 | | 1C | Z2 | ALL |
| 301R | 24 | | PX | BA | 0-0 | 31-25-11 | D05014P | | 1 | | | S00320 | | 1NC | Z2 | ALL |
| 301Y | 24 | | PX | BA | 0-0 | 31-25-11 | D05014P | | 3 | | | S00320 | | 1NO | Z2 | ALL |
| 301Z | | | | BA | 0-0 | 31-25-11 | D05014P | | 14 | | | S00320 | | DED | | ALL |
| 302B | 24 | | PM | BB | 6-0 | 33-13-11 | D04982P | | 30 | | | R00511 | | 2 | A | ALL |
| 302R | 24 | | PM | BB | 0-0 | 33-13-11 | D04982P | | 29 | | | R00511 | | 3 | A | ALL |
| 302Y | 24 | | PM | BB | 0-0 | 33-13-11 | D04982P | | 31 | | | R00511 | | 1 | A | ALL |
| A-A | | | | A | 0-0 | 34-22-15 | TS0187 | | RED | | | TB0178N | A001 | 1B | | ALL |
| A-B | | | | A | 0-0 | 34-22-15 | TS0187 | | BLU | | | TB0178N | B001 | 1B | | ALL |
| A-C | | | | | 0-0 | 34-22-15 | TS0187 | | ORG | | | TB0178N | C001 | 1B | | ALL |
| A-D | | | | | 0-0 | 34-22-15 | TS0187 | | YEL | | | TB0178N | D001 | 1B | | ALL |
| A-E | | | | | 0-0 | 34-22-15 | TS0187 | | BLK | | | TB0178N | E001 | 1B | | ALL |
| B-A | | | | | 2-8 | 33-11-13 | L00561 | | WHT | | | D04982P | | 16 | | ALL |
| B-B | | | | | 2-8 | 33-11-13 | L00561 | | BLK | | | GD04478 | | A.. | 2 | ALL |
| C-A | | | | | 0-0 | 33-14-21 | L00028 | | WHT | | | R00503 | | 2 | C | ALL |

WIRE LIST

D280T132

91-21-11

Section W1050

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1053 | 286T1053 | | | E1-3 SHELF,L ILS G/S COAX | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-31-11 | D00429C | = C5 | | | D04047J | = C1 | | | ALL |
| 01CX | | 66 | | A | 0-5 | 34-31-11 | D00429C | 5 | | | D04047J | = A1 | | | ALL |
| W1054 | 286T1054 | | | P7 INTEG PNL RIGHT SIDE | | | | | | | | | | | |
| 001 | 24 | | | PK | 6-0 | 33-14-11 | D05020P | 10 | | | R00506 | 1 | C | | ALL |
| 002 | 24 | | | PK | 6-0 | 33-14-11 | D05020P | 11 | | | R00506 | 2 | C | | ALL |
| 003 | 24 | | | PK | 6-4 | 33-14-21 | D05018P | 3 | | | R00504 | 1 | C | | ALL |
| 004 | 20 | | | PA | 4-11 | 33-14-21 | GD04476 | A.. | 2 | | L00029 | = G | C | | ALL |
| 005 | 20 | | | PA | 3-3 | 31-51-21 | D05020P | 9 | | | S00508 | 2 | 1A | | ALL |
| 006 | 24 | | | PK | 3-3 | 31-51-21 | D05020P | 8 | | | S00508 | 3 | 1A | | ALL |
| 009 | 22 | | | PA | 3-3 | 33-16-16 | D05020P | 12 | | | S00508 | 18 | 1A | | ALL |
| 010 | 22 | | | PA | 3-3 | 33-16-16 | D05020P | 13 | | | S00508 | 17 | 1A | | ALL |
| 012 | 24 | | | PK | 3-3 | 31-51-21 | D05020P | 7 | | | S00508 | 15 | 1A | | ALL |
| 013 | 22 | | | PQ | 3-2 | 33-16-16 | D04984P | 21 | | | S00508 | 13 | 1A | | ALL |
| 013Z | | | | B | 0-0 | 33-16-16 | D04984P | DED | | | S00508 | DED | | | ALL |
| 014 | 22 | | | PQ | 3-2 | 33-16-16 | D04984P | 22 | | | S00508 | 14 | 1A | | ALL |
| 014Z | | | | C | 0-0 | 33-16-16 | D04984P | DED | | | S00508 | DED | | | ALL |
| 015 | 20 | | | PA | 3-5 | 33-11-11 | GD04476 | S.. | 2 | | D00588 | 6 | | | ALL |
| 016 | 20 | | | UA | 5-3 | 33-11-11 | R00508 | REF | | FA | GD04476 | S.. | 2 | | ALL |
| 018 | 24 | | | PK | 2-10 | 34-22-25 | D04869P | 3 | | | TB0180N | C001 | 1B | | ALL |
| 019 | 24 | | | PK | 2-10 | 34-22-25 | D04869P | 4 | | | TB0180N | D001 | 1B | | ALL |
| 020 | 24 | | | PK | 2-10 | 34-22-25 | D04869P | 5 | | | TB0180N | E001 | 1B | | ALL |
| 021 | 20 | | | PA | 6-0 | 33-13-17 | D04984P | 26 | | | L00483 | = P | B | | ALL |
| 022 | 20 | | | PA | 5-5 | 33-13-17 | GD04476 | A.. | 2 | | L00483 | = G | G | | ALL |
| 024 | 22 | | | PA | 5-4 | 33-11-11 | D04984P | 1 | | | R00508 | = A | \$ | | ALL |
| 025 | 22 | | | PA | 5-4 | 33-11-11 | D04984P | 2 | | | R00508 | = B | \$ | | ALL |
| 027 | 24 | | | PK | 3-3 | 31-41-16 | D05020P | 5 | | | S00508 | 6 | 1A | | ALL |
| 028 | 24 | | | PK | 3-3 | 31-41-16 | D05020P | 6 | | | S00508 | 5 | 1A | | ALL |
| 029 | 24 | | | PK | 3-3 | 31-41-16 | D05020P | 4 | | | S00508 | 16 | 1A | | ALL |
| 201B | 24 | | | PL | 2-10 | 34-22-25 | D04869P | 2 | | | TB0180N | B001 | 1B | | ALL |
| 201R | 24 | | | PL | 0-0 | 34-22-25 | D04869P | 1 | | | TB0180N | A001 | 1B | | ALL |
| 203B | 24 | | | PL | 3-6 | 33-11-11 | D04984P | 4 | | | D00588 | 4 | | | ALL |
| 203R | 24 | | | PL | 0-0 | 33-11-11 | D04984P | 5 | | | D00588 | 5 | | | ALL |
| 204B | 24 | | | PL | 3-6 | 33-11-11 | D04984P | 6 | | | D00588 | 11 | | | ALL |
| 204R | 24 | | | PL | 0-0 | 33-11-11 | D04984P | 7 | | | D00588 | 12 | | | ALL |
| 205B | 24 | | | PL | 3-6 | 33-11-11 | D04984P | 12 | | | D00588 | 7 | | | ALL |
| 205R | 24 | | | PL | 0-0 | 33-11-11 | D04984P | 13 | | | D00588 | 8 | | | ALL |
| 206B | 24 | | | PW | 5-4 | 33-11-11 | D04984P | 3 | | | R00508 | 2 | A | | ALL |
| 206R | 24 | | | PW | 0-0 | 33-11-11 | D04984P | 9 | | | R00508 | 3 | A | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W1050
 Page 5
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1054 | 286T1054 | | | | P7 INTEG PNL RIGHT SIDE (continued) | | | | | | | | | | |
| 206Z | | | | AF | 0-0 | 33-11-11 | R00508 | REF | | FA | D04984P | 8 | | | ALL |
| 301B | 24 | PX | | BA | 6-2 | 31-25-11 | D05020P | 2 | | | S00321 | 1C | Z2 | | ALL |
| 301R | 24 | PX | | BA | 0-0 | 31-25-11 | D05020P | 1 | | | S00321 | 1NC | Z2 | | ALL |
| 301Y | 24 | PX | | BA | 0-0 | 31-25-11 | D05020P | 3 | | | S00321 | 1NO | Z2 | | ALL |
| 301Z | | | | BA | 0-0 | 31-25-11 | D05020P | 14 | | | S00321 | DED | | | ALL |
| 302B | 24 | PM | | BB | 6-0 | 33-13-13 | D04984P | 30 | | | R00512 | 2 | A | | ALL |
| 302R | 24 | PM | | BB | 0-0 | 33-13-13 | D04984P | 29 | | | R00512 | 3 | A | | ALL |
| 302Y | 24 | PM | | BB | 0-0 | 33-13-13 | D04984P | 31 | | | R00512 | 1 | A | | ALL |
| A-A | | | | A | 0-0 | 34-22-25 | TS0188 | RED | | | TB0180N | A001 | 1B | | ALL |
| A-B | | | | A | 0-0 | 34-22-25 | TS0188 | BLU | | | TB0180N | B001 | 1B | | ALL |
| A-C | | | | | 0-0 | 34-22-25 | TS0188 | ORG | | | TB0180N | C001 | 1B | | ALL |
| A-D | | | | | 0-0 | 34-22-25 | TS0188 | YEL | | | TB0180N | D001 | 1B | | ALL |
| A-E | | | | | 0-0 | 34-22-25 | TS0188 | BLK | | | TB0180N | E001 | 1B | | ALL |
| B-A | | | | | 0-0 | 33-11-13 | L00562 | WHT | | | D04984P | 16 | | | ALL |
| B-B | | | | | 0-0 | 33-11-13 | L00562 | BLK | | | GD04476 | A.. | 2 | | ALL |
| C-A | | | | | 1-11 | 33-14-21 | L00029 | WHT | | | R00504 | 2 | C | | ALL |
| W1055 | 286T1055 | | | | E1-4 SHELF,C ILS LOC COAX | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-31-31 | D00417C | = C1 | | | D04059J | = C1 | | | ALL |
| 01CX | | | 66 | A | 0-5 | 34-31-31 | D00417C | 1 | | | D04059J | = A1 | | | ALL |
| W1056 | 286T1056 | | | | FUELING PANEL P28 | | | | | | | | | | |
| 001 | 18 | UA | | | 3-0 | 28-26-11 | L00067 | 1 | K | * | D04744J | 10 | | | ALL |
| 002 | 18 | UA | | | 2-0 | 28-26-11 | L00067 | 1 | K | * | S00350 | 2 | L | * | ALL |
| 006 | 18 | UA | | | 2-0 | 28-26-11 | L00068 | 3 | K | | L00067 | 3 | K | * | ALL |
| 007 | 18 | UA | | | 2-0 | 28-26-11 | L00068 | 1 | K | * | S00351 | 2 | L | | ALL |
| 008 | 18 | UA | | | 2-0 | 28-26-11 | L00068 | 1 | K | * | S00350 | 2 | L | * | ALL |
| 010 | 18 | UA | | | 3-0 | 28-26-11 | L00067 | 2 | K | | D04746J | 8 | | | ALL |
| 011 | 18 | UA | | | 3-0 | 28-26-11 | S00350 | 3 | L | | D04746J | 7 | | | ALL |
| 020 | 18 | UA | | | 4-0 | 28-26-11 | L00068 | 2 | K | | D04746J | 18 | | | ALL |
| 021 | 18 | UA | | | 4-0 | 28-26-11 | S00351 | 3 | L | | D04746J | 17 | | | ALL |
| 022 | 18 | UA | | | 4-0 | 28-41-11 | TB0108M | 1 | 1 | | D01624 | 9 | | | ALL |
| 023 | 18 | UA | | | 3-0 | 28-41-12 | D01622 | 8 | | | TB0108M | 3 | 1 | | ALL |
| 024 | 18 | UA | | | 3-0 | 28-41-11 | TB0108M | 1 | 1 | | D01626 | 9 | | | ALL |
| 025 | 18 | UA | | | 3-0 | 28-41-12 | D01626 | 8 | | | TB0108M | 3 | 1 | | ALL |
| 026 | 18 | UA | | | 3-0 | 28-41-11 | TB0108M | 1 | 1 | | D01622 | 9 | | | ALL |
| 027 | 18 | UA | | | 4-0 | 28-41-12 | D01624 | 8 | | | TB0108M | 3 | 1 | | ALL |
| 028 | 18 | UA | | | 3-0 | 28-21-11 | D04744J | 1 | | | S00418 | 1 | J | | ALL |
| 029 | 18 | UA | | | 2-0 | 28-21-11 | S00418 | 2 | J | | SM00005 | | W | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1050

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1056 | 286T1056 | | | FUELING PANEL P28 (continued) | | | | | | | | | | | | | |
| 029 | 18 | | UA | 3-0 | 28-21-11 | S00418 | 2 | J | | | | | SM00005 | | W | | 150-199, 275-299 |
| 030 | 18 | | UA | 3-0 | 28-21-11 | S00420 | 2 | J | | | | | SM00006 | | W | | ALL |
| 031 | 18 | | UA | 3-0 | 28-21-11 | D04744J | 21 | | | | | | S00420 | 1 | J | | ALL |
| 032 | 18 | | UA | 2-0 | 28-21-11 | S00419 | 2 | J | | | | | SM00006 | | W | | ALL |
| 033 | 18 | | UA | 3-0 | 28-21-11 | D04744J | 11 | | | | | | S00419 | 1 | J | | ALL |
| 034 | 18 | | UA | 3-0 | 28-21-13 | L00063 | 2 | K | | | | | D04744J | 2 | | | ALL |
| 035 | 18 | | UA | 3-0 | 28-21-13 | L00064 | 2 | K | | | | | D04744J | 3 | | | ALL |
| 036 | 18 | | UA | 3-0 | 28-21-13 | L00174 | 3 | K | * | | | | TB0108M | 1 | 1 | | ALL |
| 037 | 18 | | UA | 1-0 | 28-21-13 | L00064 | 1 | K | * | | | | L00063 | 1 | K | * | ALL |
| 038 | 18 | | UA | 1-0 | 28-21-13 | L00064 | 3 | K | * | | | | L00063 | 3 | K | * | ALL |
| 039 | 18 | | UA | 3-0 | 28-21-13 | L00174 | 1 | K | * | | | | L00064 | 1 | K | * | ALL |
| 040 | 18 | | UA | 3-0 | 28-21-13 | L00174 | 3 | K | * | | | | L00064 | 3 | K | * | ALL |
| 041 | 18 | | UA | 2-0 | 28-21-13 | L00175 | 1 | K | * | | | | L00063 | 1 | K | * | ALL |
| 042 | 18 | | UA | 1-0 | 28-21-13 | L00175 | 3 | K | * | | | | L00063 | 3 | K | * | ALL |
| 043 | 18 | | UA | 3-0 | 28-21-13 | L00174 | 2 | K | | | | | D04744J | 22 | | | ALL |
| 044 | 18 | | UA | 3-0 | 28-21-13 | L00175 | 2 | K | | | | | D04744J | 23 | | | ALL |
| 045 | 18 | | UA | 3-0 | 28-21-13 | L00065 | 3 | K | * | | | | L00175 | 3 | K | * | ALL |
| 046 | 18 | | UA | 3-0 | 28-21-13 | L00065 | 1 | K | * | | | | L00175 | 1 | K | * | ALL |
| 047 | 18 | | UA | 1-0 | 28-21-13 | L00066 | 1 | K | | | | | L00065 | 1 | K | * | ALL |
| 048 | 18 | | UA | 1-0 | 28-21-13 | L00066 | 3 | K | * | | | | L00065 | 3 | K | * | ALL |
| 049 | 18 | | UA | 2-0 | 28-21-13 | L00065 | 2 | K | | | | | D04744J | 12 | | | ALL |
| 050 | 18 | | UA | 2-0 | 28-21-13 | L00066 | 2 | K | | | | | D04744J | 13 | | | ALL |
| 051 | 18 | | UA | 3-0 | 28-26-11 | L00067 | 3 | K | * | | | | L00066 | 3 | K | * | ALL |
| 052 | 18 | | UA | 3-0 | 28-21-13 | L00174 | 1 | K | * | | | | TB0108L | 6 | 1 | | ALL |
| 053 | 18 | | UA | 3-0 | 28-21-11 | D04744J | 4 | | | | | | S00348 | 3 | L | | ALL |
| 054 | 18 | | UA | 3-0 | 28-21-11 | S00417 | 2 | L | * | | | | S00348 | 2 | L | | ALL |
| 055 | 18 | | UA | 3-0 | 28-21-11 | D04744J | 24 | | | | | | S00417 | 3 | L | | ALL |
| 056 | 18 | | UA | 2-0 | 28-21-11 | S00349 | 2 | L | * | | | | S00417 | 2 | L | * | ALL |
| 057 | 18 | | UA | 2-0 | 28-21-11 | D04744J | 14 | | | | | | S00349 | 3 | L | | ALL |
| 058 | 18 | | UA | 3-0 | 28-21-11 | S00349 | 2 | L | * | | | | TB0108L | 6 | 1 | | ALL |
| 059 | 18 | | UA | 2-0 | 28-41-11 | D04744J | 7 | | | | | | SM00003 | | W | | ALL |
| 060 | 18 | | UA | 1-0 | 28-21-11 | S00421 | 2 | J | | | | | SM00004 | | W | | 050-099 |
| 060 | 18 | | UA | 2-0 | 28-21-11 | S00421 | 2 | J | | | | | SM00004 | | W | | 150-199, 275-299 |
| 061 | 18 | | UA | 4-0 | 28-21-11 | D04744J | 29 | | | | | | D03056 | 10 | | | ALL |
| 062 | 18 | | UA | 4-0 | 28-21-11 | D04746J | 9 | | | | | | S00345 | 3 | L | | ALL |
| 063 | 18 | | UA | 4-0 | 28-21-11 | D04746J | 10 | | | | | | S00345 | 2 | L | | ALL |
| 064 | 18 | | UA | 3-0 | 28-21-12 | D04744J | 8 | | | | | | S00347 | 1 | J | | ALL |
| 065 | 18 | | UA | 3-0 | 28-21-12 | TB0108M | 1 | 1 | | | | | S00347 | 2 | J | | ALL |
| 066 | 18 | | UA | 3-0 | 28-21-12 | D04744J | 9 | | | | | | S00416 | 1 | J | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1050
Page 7
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1056 | 286T1056 | | | FUELING PANEL P28 (continued) | | | | | | | | | | | | |
| 067 | 18 | | UA | | 3-0 | 28-21-12 | S00416 | | 2 | J | | TB0108M | 1 | 1 | | ALL |
| 068 | 18 | | UA | | 3-0 | 28-21-12 | D04744J | | 16 | | | TB0108M | 1 | 1 | | ALL |
| 069 | 18 | | UA | | 3-0 | 28-41-12 | D04744J | | 17 | | | TB0108M | 3 | 1 | | ALL |
| 070 | 18 | | UA | | 3-0 | 28-21-11 | D04744J | | 19 | | | TB0108L | 6 | 1 | | ALL |
| 072 | 18 | | UA | | 3-0 | 28-21-11 | D04744J | | 5 | | | S00421 | 1 | J | | ALL |
| 073 | 18 | | UA | | 3-0 | 28-41-11 | D04744J | | 6 | | | S00457 | 1 | J | | ALL |
| 076 | 18 | | UA | | 2-0 | 28-41-11 | D01622 | | 10 | | | GDX0001 | S.. | N | | ALL |
| 077 | 18 | | UA | | 2-0 | 28-41-11 | D01626 | | 10 | | | GDX0002 | S.. | N | | ALL |
| 078 | 18 | | UA | | 2-0 | 28-41-11 | D01624 | | 10 | | | GDX0002 | S.. | N | | ALL |
| 080 | 18 | | UA | | 3-0 | 28-41-11 | D01626 | | 2 | | | SM00001 | | W | | ALL |
| 081 | 18 | | UA | | 3-0 | 28-41-11 | D01626 | | 1 | | | SM00002 | | W | | ALL |
| 082 | 18 | | UA | | 2-0 | 28-41-11 | D04746J | | 11 | | | SM00001 | | W | | ALL |
| 083 | 18 | | UA | | 3-0 | 28-41-11 | D01624 | | 2 | | | SM00001 | | W | | ALL |
| 084 | 18 | | UA | | 3-0 | 28-41-11 | D01624 | | 1 | | | SM00002 | | W | | ALL |
| 085 | 18 | | UA | | 2-0 | 28-41-11 | D04746J | | 1 | | | SM00002 | | W | | ALL |
| 086 | 18 | | UA | | 3-0 | 28-41-11 | D01622 | | 2 | | | SM00001 | | W | | ALL |
| 087 | 18 | | UA | | 3-0 | 28-41-11 | D01622 | | 1 | | | SM00002 | | W | | ALL |
| 088 | 18 | | UA | | 2-0 | 28-21-11 | S00457 | | 2 | J | | SM00003 | | W | | ALL |
| 089 | 18 | | UA | | 1-0 | 28-21-11 | SM00004 | | | W | | SM00003 | | W | | ALL |
| 090 | 18 | | UA | | 1-0 | 28-21-11 | SM00004 | | | W | | SM00005 | | W | | ALL |
| 091 | 18 | | UA | | 1-0 | 28-21-11 | SM00006 | | | W | | SM00005 | | W | | ALL |
| 202B | 20 | UB | AB | | 4-0 | 28-41-11 | D04746J | | 3 | | | D01622 | | 6 | | ALL |
| 202R | 20 | UB | AB | | 0-0 | 28-41-11 | D04746J | | 4 | | | D01622 | | 7 | | ALL |
| 205B | 20 | UB | AE | | 4-0 | 28-41-11 | D04746J | | 23 | | | D01626 | | 6 | | ALL |
| 205R | 20 | UB | AE | | 0-0 | 28-41-11 | D04746J | | 24 | | | D01626 | | 7 | | ALL |
| 208B | 20 | UB | AH | | 4-0 | 28-41-11 | D04746J | | 13 | | | D01624 | | 6 | | ALL |
| 208R | 20 | UB | AH | | 0-0 | 28-41-11 | D04746J | | 14 | | | D01624 | | 7 | | ALL |
| 301B | 20 | UC | MA | | 4-0 | 28-41-11 | D04746J | | 25 | | | D01626 | | 3 | | ALL |
| 301R | 20 | UC | MA | | 0-0 | 28-41-11 | D04746J | | 26 | | | D01626 | | 4 | | ALL |
| 301Y | 20 | UC | MA | | 0-0 | 28-41-11 | D04746J | | 22 | | | D01626 | | 5 | | ALL |
| 302B | 20 | UC | MB | | 4-0 | 28-41-11 | D04746J | | 15 | | | D01624 | | 3 | | ALL |
| 302R | 20 | UC | MB | | 0-0 | 28-41-11 | D04746J | | 16 | | | D01624 | | 4 | | ALL |
| 302Y | 20 | UC | MB | | 0-0 | 28-41-11 | D04746J | | 12 | | | D01624 | | 5 | | ALL |
| 303B | 20 | UC | MC | | 4-0 | 28-41-11 | D04746J | | 5 | | | D01622 | | 3 | | ALL |
| 303R | 20 | UC | MC | | 0-0 | 28-41-11 | D04746J | | 6 | | | D01622 | | 4 | | ALL |
| 303Y | 20 | UC | MC | | 0-0 | 28-41-11 | D04746J | | 2 | | | D01622 | | 5 | | ALL |
| 401B | 20 | UD | AJ | | 4-0 | 28-21-11 | D04744J | | 25 | | | D03056 | | 4 | | ALL |
| 401G | 20 | UD | AJ | | 0-0 | 28-21-11 | D04744J | | 26 | | | D03056 | | 5 | | ALL |
| 401R | 20 | UD | AJ | | 0-0 | 28-21-11 | D04744J | | 27 | | | D03056 | | 6 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1050

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|------|--------------------------------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1056 | 286T1056 | | | | FUELING PANEL P28 (continued) | | | | | | | | | | |
| 401Y | 20 | UD | AJ | 0-0 | 28-21-11 | D04744J | 28 | | | D03056 | 7 | | | ALL | |
| W1057 | 286T1057 | | | | E1-4 SHELF,C ILS G/S COAX | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-31-31 | D00417C | = C5 | | | D04057J | = C1 | | | ALL | |
| 01CX | | 66 | A | 0-5 | 34-31-31 | D00417C | 5 | | | D04057J | = A1 | | | ALL | |
| W1058 | 286T1058 | | | | P19 INTEGRATION | | | | | | | | | | |
| 001 | 22 | PA | | 4-2 | 33-24-11 | D05160J | 1 | | | TB0146Y | C016 | BJ | | 050-099, 275-299 | |
| 001 | 22 | PA | | 4-2 | 33-24-11 | TB0146Y | C016 | BJ | | D05160J | 1 | | | 150-199 | |
| 002 | 22 | PA | | 3-11 | 33-25-11 | D05178J | 9 | | | TB0146Y | A005 | BJ | | ALL | |
| 003 | 22 | PA | | 3-11 | 33-25-11 | D05160J | 11 | | | TB0146Y | A005 | BJ | | ALL | |
| 004 | 18 | PA | | 3-9 | 26-13-11 | D05178J | 19 | DL | | TB0174H | 3 | 2 | | 050-099 | |
| 004 | 18 | PA | | 3-9 | 26-13-11 | D05178J | 19 | DL | | TB0174G | 3 | 2 | | 150-157 | |
| 004 | 22 | PA | | 3-11 | 33-25-11 | D05160J | 10 | | | TB0146Y | C005 | BJ | | 275-299 | |
| 005 | 20 | PA | | 4-5 | 33-26-21 | D05178J | 1 | | | TB0146Y | A028 | BJ | | 050-099, 150-199 | |
| 005 | 20 | PA | | 4-8 | 33-26-21 | D05178J | 1 | | | TB0146Z | 35 | BJ | | 275-299 | |
| 007 | 20 | PA | | 4-8 | 33-26-21 | TB0146Z | 35 | BJ | | D05160J | 4 | | | 050-099 | |
| 007 | 20 | PA | | 4-8 | 33-26-21 | D05160J | 4 | | | TB0146Z | 35 | BJ | | 150-199 | |
| 007 | 22 | PA | | 4-8 | 33-26-21 | D05160J | 4 | | | TB0146Z | 35 | BJ | | 275-299 | |
| 009 | 22 | PA | | 3-11 | 33-26-11 | D05178J | 7 | | | TB0146Y | A006 | BJ | | 050-099, 275-299 | |
| 009 | 22 | PA | | 4-7 | 33-26-11 | D05178J | 7 | | | TB0174Z | 36 | BJ | | 150-199 | |
| 010 | 22 | PA | | 3-11 | 33-26-11 | TB0146Y | A006 | BJ | | D05160J | 7 | | | 050-099, 275-299 | |
| 010 | 22 | PA | | 4-7 | 33-26-11 | D05160J | 7 | | | TB0174Z | 36 | BJ | | 150-199 | |
| 011 | 22 | PA | | 4-8 | 33-26-11 | TB0146Z | 36 | BJ | | D05160J | 8 | | | 050-099, 275-299 | |
| 011 | 22 | PA | | 4-8 | 33-26-11 | D05160J | 8 | | | TB0146Z | 36 | BJ | | 150-199 | |
| 012 | 16 | PA | | 3-10 | 38-13-11 | D05160J | 23 | | | TB0146G | 4 | 2 | | 150-199, 275-299 | |
| 015 | 20 | PA | | 2-3 | 33-44-11 | D08080J | 11 | | | TB0146F | A003 | 2 | | ALL | |
| 016 | 20 | PA | | 3-9 | 26-13-11 | D05160J | 30 | | | TB0174X | C001 | BJ | | 050-099, 150-199 | |
| 017 | 24 | PK | | 4-4 | 33-24-11 | D05178J | 17 | | | TB0146H | 22 | 2 | | ALL | |
| 018 | 24 | PK | | 3-10 | 21-24-11 | D05178J | 2 | | | TB0146F | C003 | 2 | | 050-099, 150-199 | |
| 019 | 22 | PA | | 3-11 | 38-32-12 | D05160J | 2 | | | TB0146X | C008 | BJ | | 050-099 | |
| 019 | 20 | PA | | 3-11 | 38-32-12 | D05160J | 2 | | | TB0146X | C008 | BJ | | 150-156, 162-165, 275-276 | |
| 019 | 20 | PA | | 3-11 | 38-32-16 | D05160J | 2 | | | TB0146X | C008 | BJ | | 157, 166-199, 277-299 | |
| 022 | 22 | PA | | 4-7 | 33-24-11 | D05160J | 13 | | | TB0174Z | 36 | BJ | | 050-099 | |
| 022 | 20 | PA | | 4-3 | 33-24-11 | D05160J | 13 | | | TB0146Z | 20 | BJ | | 275-276 | |
| 022 | 20 | PQ | AV | 4-3 | 33-24-11 | D05160J | 13 | | | TB0146Z | 20 | BJ | | 277-299 | |
| 022Z | | | AV | 0-0 | 33-24-11 | D05160J | DED | | | TB0146Z | DED | | | 277-299 | |
| 024 | 20 | PA | | 4-8 | 33-26-11 | D05160J | 15 | | | TB0146Z | 35 | BJ | | 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W1050

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1058 | 286T1058 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 025 | 22 | | PA | | 3-10 | 52-51-11 | D05178J | | 21 | | TB0174F | A008 | 2 | | ALL |
| 026 | 22 | | PA | | 3-10 | 52-51-11 | D05178J | | 20 | | TB0174F | C008 | 2 | | ALL |
| 031 | 20 | | PA | | 4-5 | 33-26-21 | D05160J | | 16 | | TB0160Y | C017 | BJ | | 050-099, 150-157 |
| 031 | 20 | | PA | | 3-11 | 33-26-21 | D05160J | | 16 | | TB0146X | A007 | BJ | | 162-199 |
| 032 | 20 | | PA | | 4-5 | 33-26-21 | D05160J | | 25 | | TB0160Y | C017 | BJ | | 280-299 |
| 035 | 22 | | PA | | 4-4 | 33-51-11 | D05178J | | 22 | | TB0160Y | A015 | BJ | | ALL |
| 036 | 24 | | PK | | 4-5 | 35-21-11 | D05178J | | 6 | | TB0160G | 18 | 2 | | ALL |
| 038 | 20 | | PA | | 3-11 | 33-26-21 | TB0146Y | C005 | BJ | | D05160J | 12 | | | 050-099 |
| 038 | 20 | | PA | | 3-11 | 33-26-21 | D05160J | | 12 | | TB0146X | A007 | BJ | | 150-157 |
| 038 | 20 | | PA | | 4-5 | 33-26-21 | D05160J | | 12 | | TB0160Y | C017 | BJ | | 162-199 |
| 038 | 22 | | PA | | 3-11 | 33-26-21 | D05160J | | 16 | | TB0146X | A007 | BJ | | 275-278 |
| 038 | 22 | | PA | | 3-11 | 33-26-21 | D05160J | | 16 | | TB0146X | B007 | BJ | | 280-299 |
| 040 | 22 | | PA | | 4-3 | 33-25-11 | D05160J | | 24 | | TB0174D | C021 | 2 | | 050-099, 150-199 |
| 041 | 20 | | PA | | 4-9 | 38-32-12 | D05160J | | 3 | | TB0146Y | A037 | BJ | | 050-099, 150-156, 162-165, 275-276 |
| 041 | 20 | | PA | | 4-9 | 38-32-16 | D05160J | | 3 | | TB0146Y | A037 | BJ | | 157, 166-199, 277-299 |
| 042 | 22 | | PA | | 4-3 | 33-25-11 | D05160J | | 26 | | TB0174D | A021 | 2 | | 050-099, 150-199 |
| 064 | 20 | | PA | | 4-6 | 26-13-12 | D05160J | | 9 | | TB0174X | A032 | BJ | | 050-099 |
| 064 | 20 | | PA | | 4-10 | 26-13-12 | D05160J | | 9 | | TB0146X | C041 | BJ | | 162-199 |
| 066 | 20 | | PA | | 4-6 | 26-13-11 | D05160J | | 17 | | TB0174X | B031 | BJ | | 050-099 |
| 067 | 20 | | PA | | 4-6 | 26-13-11 | D05160J | | 18 | | TB0174X | C031 | BJ | | 050-099 |
| 068 | 20 | | PA | | 4-9 | 26-13-11 | D05160J | | 20 | | TB0174Z | 42 | BJ | | 050-099 |
| 069 | 20 | | PA | | 4-9 | 26-13-11 | D05160J | | 34 | | TB0174Z | 43 | BJ | | 050-099 |
| 070 | 20 | | PA | | 4-9 | 26-13-11 | D05160J | | 22 | | TB0174Z | 41 | BJ | | 050-099 |
| 071 | 20 | | PA | | 4-6 | 26-13-11 | D05160J | | 19 | | TB0174X | D031 | BJ | | 050-099 |
| 073 | 20 | | PA | | 4-6 | 26-13-12 | D05160J | | 33 | | TB0174X | A031 | BJ | | 050-099 |
| 075 | 22 | | PA | | 4-3 | 33-25-11 | D05160J | | 10 | | TB0146Y | C017 | BJ | | 050-099 |
| 076 | 18 | | PA | | 4-8 | 26-13-11 | D05178J | | 19 | DL | TB0174H | 39 | 2 | | 162-199 |
| 077 | 18 | | PA | | 4-8 | 26-13-11 | TB0174H | | 39 | 2 | D05160J | 29 | DK | | 162-199 |
| 078 | 20 | | PA | | 4-9 | 26-13-12 | D05160J | | 34 | | TB0174Y | A042 | BJ | | 162-199 |
| 079 | 20 | | PA | | 4-9 | 26-13-12 | D05160J | | 22 | | TB0174Y | C042 | BJ | | 162-199 |
| 080 | 20 | | PA | | 4-9 | 26-13-12 | D05160J | | 20 | | TB0174Y | A043 | BJ | | 162-199 |
| 081 | 20 | | PA | | 4-10 | 26-13-12 | D05160J | | 33 | | TB0146X | D041 | BJ | | 162-199 |
| 082 | 20 | | PA | | 4-4 | 26-13-12 | D05160J | | 27 | | TB0174Y | C026 | BJ | | 050-099 |
| 082 | 20 | | PA | | 4-9 | 26-13-12 | D05160J | | 27 | | TB0174Y | C043 | BJ | | 162-199 |
| 084 | 22 | | PA | | 4-11 | 21-66-11 | D05178J | | 18 | | TB0146Y | C045 | BJ | | 050-099, 162-199 |
| 104 | 20 | | PA | | 4-0 | 25-42-11 | TB0146Y | A011 | BJ | | D05160J | 31 | | | 050-099 |
| 104 | 20 | | PA | | 4-0 | 25-42-11 | D05160J | | 31 | | TB0146Y | A011 | BJ | | 150-199, 275-299 |
| 105 | 20 | | PA | | 4-5 | 33-26-11 | D05160J | | 15 | | TB0146Y | A028 | BJ | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1050

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|------------------------------------|----|------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1058 | 286T1058 | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 106 | 20 | PA | | 4-2 | 33-24-11 | TB0146Z | 13 | BJ | | D05160J | 13 | | | 150-199 | |
| 107 | 20 | PA | | 4-2 | 33-24-11 | TB0146Z | 14 | BJ | | D05160J | 14 | | | 150-199 | |
| 201B | 22 | PB | A | 3-3 | 21-51-12 | D08080J | 1 | | | D05178J | 15 | | | ALL | |
| 201R | 22 | PB | A | 0-0 | 21-51-12 | D08080J | 2 | | | D05178J | 16 | | | ALL | |
| 202B | 24 | PL | B | 3-3 | 21-61-21 | D08080J | 3 | | | D05178J | 4 | | | ALL | |
| 202R | 24 | PL | B | 0-0 | 21-61-21 | D08080J | 4 | | | D05178J | 5 | | | ALL | |
| 203B | 24 | PL | C | 3-3 | 21-61-21 | D08080J | 5 | | | D05178J | 12 | | | ALL | |
| 203R | 24 | PL | C | 0-0 | 21-61-21 | D08080J | 6 | | | D05178J | 3 | | | ALL | |
| 205B | 20 | PB | E | 3-3 | 21-65-11 | D08080J | 9 | | | D05178J | 13 | | | ALL | |
| 205R | 20 | PB | E | 0-0 | 21-65-11 | D08080J | 10 | | | D05178J | 14 | | | ALL | |
| 206B | 22 | PB | F | 4-3 | 23-31-14 | D05160J | 6 | | | TB0174Z | 24 | BJ | | ALL | |
| 206R | 22 | PB | F | 0-0 | 23-31-14 | D05160J | 5 | | | TB0174Z | 23 | BJ | | ALL | |
| 208B | 24 | PL | IH | 3-3 | 21-61-61 | D05178J | 11 | | | D08080J | 19 | | | ALL | |
| 208R | 24 | PL | IH | 0-0 | 21-61-61 | D05178J | 10 | | | D08080J | 18 | | | ALL | |
| 209B | 24 | PL | II | 4-7 | 21-61-71 | D05178J | 24 | | | TB0160F | A025 | 2 | | ALL | |
| 209R | 24 | PL | II | 0-0 | 21-61-71 | D05178J | 25 | | | TB0160F | C025 | 2 | | ALL | |
| 210B | 24 | PL | IJ | 4-7 | 21-61-71 | D05178J | 27 | | | TB0160F | A027 | 2 | | ALL | |
| 210R | 24 | PL | IJ | 0-0 | 21-61-71 | D05178J | 26 | | | TB0160F | C027 | 2 | | ALL | |
| 211B | 20 | PB | IK | 4-6 | 21-65-11 | D05178J | 28 | | | TB0160F | A021 | 2 | | ALL | |
| 211R | 20 | PB | IK | 0-0 | 21-65-11 | D05178J | 29 | | | TB0160F | C021 | 2 | | ALL | |
| 212B | 20 | PB | IL | 3-3 | 21-65-11 | D05178J | 30 | | | D08080J | 16 | | | 050-099, 150-199 | |
| 212B | 20 | PB | IL | 3-3 | 21-65-11 | D08080J | 16 | | | D05178J | 30 | | | 275-299 | |
| 212R | 20 | PB | IL | 0-0 | 21-65-11 | D05178J | 31 | | | D08080J | 17 | | | 050-099, 150-199 | |
| 212R | 20 | PB | IL | 0-0 | 21-65-11 | D08080J | 17 | | | D05178J | 31 | | | 275-299 | |
| 500 | 22 | PA | | 4-8 | 33-24-11 | D05160J | 14 | | | TB0174Z | 38 | BJ | | 050-099 | |
| 500 | 20 | PA | | 4-8 | 33-24-11 | D05160J | 14 | | | TB0174Z | 38 | BJ | | 275-276 | |
| 500 | 20 | PQ | TY | 4-8 | 33-24-11 | D05160J | 14 | | | TB0174Z | 38 | BJ | | 277-299 | |
| 500Z | | | TY | 0-0 | 33-24-11 | D05160J | DED | | | TB0174Z | DED | | | 277-299 | |
| 601 | 18 | PA | | 3-9 | 26-13-11 | D05160J | 29 | DK | | TB0174H | 3 | 2 | | 050-099 | |
| 601 | 18 | PA | | 3-9 | 26-13-11 | D05160J | 29 | DK | | TB0174G | 3 | 2 | | 150-157 | |
| 604 | 22 | PA | | 4-0 | 33-25-11 | D05160J | 28 | | | TB0146X | C010 | BJ | | 050-099, 150-199 | |
| 605 | 22 | PA | | 1-11 | 33-26-21 | TB0146Z | 35 | BJ | | TB0146X | D008 | BJ | | 275-278 | |
| 618 | 22 | PA | | 3-11 | 33-26-21 | D05160J | 12 | | | TB0146X | D008 | BJ | | 275-278 | |
| 618 | 22 | PA | | 4-8 | 33-26-21 | D05160J | 12 | | | TB0146Z | 35 | BJ | | 280-299 | |
| W1059 | 286T1059 | E1-5 SHELF,R ILS LOC COAX | | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-31-21 | D00377C | =C1 | | | D04049J | =C1 | | | ALL | |
| 01CX | | 66 | A | 0-5 | 34-31-21 | D00377C | 1 | | | D04049J | =A1 | | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W1050
Page 11 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1060 | 286T1060 | | | P19 INTEGRATION | | | | | | | | | | | | | |
| 001 | 24 | | PK | 3-0 | 33-21-11 | D05170J | | 1 | | | | | TB0146Z | 29 | BJ | | ALL |
| 002 | 24 | | PK | 6-0 | 33-21-11 | D04290J | | 28 | | | | | S01634 | 3 | C | | 275-299 |
| 004 | 22 | | PA | 3-0 | 33-21-21 | D05088J | | 2 | | | | | TB0146Z | 33 | BJ | | 050-099 |
| 004 | 20 | | PA | 3-0 | 33-21-21 | D05088J | | 2 | | | | | TB0146Z | 33 | BJ | | 150-199, 275-299 |
| 005 | 22 | | PA | 3-0 | 33-21-21 | D10794 | | X1 | | | | | TB0146Z | 33 | BJ | | 050-099 |
| 005 | 22 | | PA | 5-0 | 33-21-21 | D10794 | | X1 | | | | | TB0146Z | 33 | BJ | | 150-199 |
| 005 | 22 | | PA | 4-0 | 33-21-21 | D03556 | | B2 | | | | | TB0146Z | 33 | BJ | | 275-299 |
| 006 | 20 | | PA | 6-0 | 33-21-21 | D03556 | | X2 | | | | | GDX0001 | A.. | 2 | | 050-099 |
| 006 | 20 | | PA | 5-0 | 33-21-21 | D03556 | | X2 | | | | | GDX0001 | A.. | 2 | | 150-199, 275-299 |
| 007 | 22 | | PA | 3-0 | 33-21-21 | D10794 | | A2 | | | | | TB0146Z | 33 | BJ | | ALL |
| 008 | 22 | | PA | 4-0 | 33-21-21 | TB0146Z | | 34 | BJ | | | | D11922 | B2 | | | 162-199 |
| 008 | 22 | | PA | 4-0 | 33-21-21 | D05148J | | 1 | | | | | S01639 | 3 | C | * | 275-299 |
| 009 | 22 | | PA | 3-0 | 33-21-21 | TB0174X | | B001 | BJ | | | | D05148J | 2 | | | ALL |
| 010 | 22 | | PA | 3-0 | 33-21-21 | D04290J | | 4 | | | | | TB0146Z | 33 | BJ | | 050-099, 150-199 |
| 010 | 24 | | PK | 3-0 | 33-21-21 | D04290J | | 4 | | | | | TB0146Z | 33 | BJ | | 275-299 |
| 011 | 22 | | PA | 4-0 | 33-21-21 | D04290J | | 5 | | | | | D13358 | C3 | | | 050-099 |
| 011 | 22 | | PA | 5-0 | 33-21-21 | D04290J | | 5 | | | | | D13358 | C3 | | | 150-199 |
| 011 | 24 | | PK | 4-0 | 33-21-21 | D04290J | | 5 | | | | | D03556 | X1 | | | 275-299 |
| 012 | 22 | | PA | 3-0 | 33-21-21 | D05148J | | 3 | | | | | TB0174Y | A013 | BJ | | 050-099 |
| 012 | 22 | | PA | 3-0 | 33-21-21 | TB0174Y | | A013 | BJ | | | | D05148J | 3 | | | 150-199 |
| 012 | 22 | | PA | 4-0 | 33-21-21 | S00435 | | 2 | C | | | | D05148J | 5 | | | 275-299 |
| 014 | 22 | | PA | 4-0 | 33-21-21 | D04290J | | 57 | | | | | D05138J | 2 | | | 050-099 |
| 014 | 22 | | PA | 5-0 | 33-21-21 | D04290J | | 57 | | | | | D05138J | 2 | | | 150-199 |
| 014 | 22 | | PA | 4-0 | 33-21-21 | S00800 | | 2 | C | | * | | D05138J | 2 | | | 275-299 |
| 017 | 22 | | PA | 5-0 | 33-21-21 | D03556 | | B1 | | | | | TB0146Y | A012 | BJ | | 050-099, 150-199 |
| 017 | 22 | | PA | 4-0 | 33-21-21 | S01639 | | 2 | C | | * | | D05148J | 34 | | | 275-299 |
| 018 | 22 | | PA | 3-0 | 33-21-21 | D05148J | | 5 | | | | | TB0146Y | A012 | BJ | | 050-099 |
| 018 | 22 | | PA | 3-0 | 33-21-21 | TB0146Y | | A012 | BJ | | | | D05148J | 5 | | | 150-199 |
| 018 | 22 | | PA | 3-0 | 33-21-21 | S00435 | | 1 | C | | * | | D05138J | 4 | | | 275-278 |
| 018 | 22 | | PA | 3-0 | 33-21-21 | S00845 | | 3 | C | | | | D05138J | 4 | | | 280-299 |
| 019 | 22 | | PA | 4-0 | 33-21-21 | TB0146Z | | 34 | BJ | | | | D03556 | B2 | | | 162-199 |
| 019 | 22 | | PA | 4-0 | 33-21-21 | D05138J | | 5 | | | | | S01639 | 3 | C | * | 275-299 |
| 01A | 20 | | PA | 5-0 | 33-22-42 | D05148J | | 14 | | | | | S01640 | 2 | C | | 275-299 |
| 01B | 20 | | PA | 5-0 | 33-22-42 | D05148J | | 44 | | | | | S01640 | 1 | C | | 275-299 |
| 01C | 20 | | PA | 5-0 | 33-22-42 | D05148J | | 45 | | | | | S01640 | 3 | C | | 275-299 |
| 01T | 22 | | PA | 2-0 | 33-21-21 | S00435 | | 1 | C | | * | | S00845 | 2 | C | | 280-299 |
| 01U | 22 | | PA | 2-0 | 33-21-21 | TB0146Z | | 33 | BJ | | | | TB0146Y | C012 | BJ | | 280-299 |
| 01V | 18 | | PA | 4-0 | 33-22-31 | D05148J | | 22 | DK | | | | TB0146H | 1 | 2 | | 280-299 |
| 01W | 20 | | PA | 4-0 | 33-24-11 | D05148J | | 41 | | | | | TB0146Y | A014 | BJ | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|---|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | | |
| 01X | 20 | | PA | | 4-0 | 33-24-11 | D05148J | 40 | | | | | | TB0146Y | C014 | BJ | | 280-299 |
| 020 | 22 | | PA | | 3-0 | 33-21-21 | TB0146Z | 34 | BJ | | | | | D10794 | D2 | | | 162-199 |
| 020 | 22 | | PA | | 2-0 | 33-21-21 | S01639 | 3 | C | * | | | | S00435 | 3 | C | * | 275-299 |
| 021 | 22 | | PA | | 3-0 | 33-24-11 | TB0146Z | 19 | BJ | | | | | D05170J | 36 | | | 162-199 |
| 021 | 20 | | PA | | 3-0 | 33-24-11 | D04290J | 52 | | | | | | TB0174Z | 38 | BJ | | 275-299 |
| 022 | 22 | | PA | | 3-0 | 33-24-11 | TB0146Z | 20 | BJ | | | | | D05170J | 35 | | | 162-199 |
| 022 | 20 | | PA | | 3-0 | 33-24-11 | D04290J | 51 | | | | | | TB0174Z | 37 | BJ | | 275-299 |
| 025 | 20 | | PA | | 5-0 | 33-51-11 | D06410J | 2 | | | | | | TB0160G | 37 | 2 | | 050-099 |
| 025 | 20 | | PA | | 2-0 | 33-51-11 | D06410J | 2 | | | | | | TB0160G | 37 | 2 | | 150-199, 275-299 |
| 026 | 22 | | PA | | 3-0 | 33-21-21 | D05138J | 3 | | | | | | TB0146Y | A012 | BJ | | 050-099 |
| 026 | 22 | | PA | | 3-0 | 33-21-21 | D05138J | 3 | | | | | | TB0174Y | A013 | BJ | | 150-199 |
| 026 | 22 | | PA | | 2-0 | 33-21-21 | S00435 | 1 | C | * | | | | S01639 | 1 | C | * | 275-299 |
| 027 | 22 | | PA | | 4-0 | 21-61-21 | D05088J | 4 | | | | | | D05138J | 9 | | | ALL |
| 028 | 24 | | PK | | 3-0 | 33-21-31 | D05170J | 6 | | | | | | TB0174Y | A006 | BJ | | 050-099, 150-162, 166-199, 275-299 |
| 028 | 24 | | PK | | 4-0 | 33-21-31 | D05170J | 6 | | | | | | TB0174Y | A006 | BJ | | 163-165 |
| 029 | 24 | | PK | | 5-0 | 33-21-31 | D13358 | A2 | | | | | | TB0174Y | C012 | BJ | | 050-099 |
| 029 | 24 | | PK | | 5-0 | 33-21-31 | D13358 | A2 | | | | | | TB0174X | A002 | BJ | | 150-157 |
| 029 | 24 | | PK | | 5-0 | 33-21-31 | D13358 | A2 | | | | | | TB0174Y | C013 | BJ | | 162-199 |
| 029 | 24 | | PK | | 3-0 | 33-21-31 | D04290J | 19 | | | | | | TB0174X | A002 | BJ | | 275-299 |
| 030 | 24 | | PK | | 5-0 | 33-21-31 | D13360 | X2 | | | | | | TB0174Y | C006 | BJ | | 050-099 |
| 030 | 24 | | PK | | 4-0 | 33-21-31 | D13360 | X2 | | | | | | TB0174Y | C006 | BJ | | 150-199 |
| 030 | 24 | | PK | | 3-0 | 33-21-31 | D05138J | 8 | | | | | | TB0174Y | C006 | BJ | | 275-299 |
| 031 | 24 | | PK | | 5-0 | 33-21-31 | D13362 | Y1 | | | | | | TB0146Y | A032 | BJ | | 155-157, 166-199 |
| 031 | 20 | | PA | | 2-0 | 33-22-11 | D05170J | 4 | | | | | | TB0146G | 32 | 2 | | 275-278 |
| 031 | 20 | | PA | | 4-0 | 33-22-11 | D05170J | 4 | | | | | | TB0146H | 1 | 2 | | 280-299 |
| 032 | 20 | | PA | | 4-0 | 33-22-11 | D05170J | 5 | | | | | | D05148J | 8 | | | ALL |
| 033 | 20 | | PA | | 2-0 | 33-22-11 | D05170J | 7 | | | | | | D04290J | 14 | | | ALL |
| 034 | 22 | | PA | | 6-0 | 33-22-11 | D00108 | A1 | | | | | | TB0174X | A001 | BJ | | 050-099 |
| 034 | 20 | | PA | | 4-0 | 33-22-11 | D00108 | A1 | | | | | | TB0174X | A001 | BJ | | 150-154, 162-165, 275-299 |
| 034 | 20 | | PQ | BI | 6-0 | 33-22-11 | D00108 | A1 | | | | | | TB0174X | A001 | BJ | | 155-156, 166 |
| 034 | 20 | | PA | | 6-0 | 33-22-11 | D00108 | A1 | | | | | | TB0174X | A001 | BJ | | 157, 167-199 |
| 034Z | | | | BI | 0-0 | 33-22-11 | D00108 | DED | | | | | | TB0174X | DED | | | 155-156, 166 |
| 035 | 24 | | PK | | 4-0 | 33-22-11 | D05148J | 9 | | | | | | D04290J | 16 | | | ALL |
| 036 | 22 | | PA | | 4-0 | 33-22-11 | D00108 | A2 | | | | | | TB0174Z | 9 | BJ | | 050-099 |
| 036 | 20 | | PA | | 4-0 | 33-22-11 | D00108 | A2 | | | | | | TB0174Z | 9 | BJ | | 150-154, 157-165, 167-199, 275-299 |
| 036 | 20 | | PQ | BK | 4-0 | 33-22-11 | D00108 | A2 | | | | | | TB0174Z | 9 | BJ | | 155-156, 166 |

WIRE LIST
D280T132

91-21-11
Section W1060
Page 2
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | | |
| 036Z | | | | BK | 0-0 | 33-22-11 | D00108 | | DED | | | | | TB0174Z | DED | | | 155-156, 166 |
| 037 | 20 | PA | | | 5-0 | 33-22-11 | GDX0001 | | A.. | 2 | | | | D00108 | X2 | | | 050-099 |
| 037 | 20 | PA | | | 4-0 | 33-22-11 | GDX0001 | | A.. | 2 | | | | D00108 | X2 | | | 150-199, 275-299 |
| 038 | 20 | PA | | | 3-0 | 33-22-11 | D04290J | | | 17 | | | | D00108 | X1 | | | ALL |
| 039 | 24 | PK | | | 2-0 | 33-22-11 | D04290J | | | 18 | | | | D05090J | 1 | | | ALL |
| 040 | 24 | PK | | | 2-0 | 33-22-11 | D04290J | | | 15 | | | | D05090J | 2 | | | ALL |
| 041 | 24 | PK | | | 4-0 | 33-22-11 | D05148J | | | 11 | | | | D05090J | 3 | | | ALL |
| 042 | 24 | PK | | | 4-0 | 33-22-11 | D05148J | | | 12 | | | | D05090J | 4 | | | ALL |
| 043 | 22 | PA | | | 4-0 | 33-22-41 | D10794 | | | B3 | | | | TB0160Y | A016 | BJ | | 050-099 |
| 043 | 22 | PA | | | 3-0 | 33-22-41 | D10794 | | | B3 | | | | TB0160Y | A016 | BJ | | 150-199, 275-299 |
| 044 | 22 | PA | | | 5-0 | 33-22-41 | D04290J | | | 6 | | | | TB0160Y | A016 | BJ | | 275-299 |
| 045 | 22 | PA | | | 5-0 | 33-22-41 | D04290J | | | 8 | | | | TB0160Y | A016 | BJ | | ALL |
| 046 | 22 | PA | | | 6-0 | 33-22-41 | TB0160Y | | C015 | | BJ | | | D01758 | A3 | | | ALL |
| 047 | 22 | PA | | | 3-0 | 33-22-41 | D04290J | | | 9 | | | | TB0160Y | C016 | BJ | | 275-299 |
| 048 | 22 | PA | | | 2-0 | 33-22-41 | D01758 | | | A2 | | | | D03558 | A1 | | | ALL |
| 049 | 20 | PA | | | 6-0 | 33-22-41 | D01758 | | | X2 | | | | GDX0002 | A.. | 2 | | 050-099 |
| 049 | 20 | PA | | | 5-0 | 33-22-41 | D01758 | | | X2 | | | | GDX0002 | A.. | 2 | | 150-199, 275-299 |
| 050 | 22 | PA | | | 7-0 | 33-22-41 | D01758 | | | X1 | | | | TB0160Y | C016 | BJ | | 050-099 |
| 050 | 22 | PA | | | 4-0 | 33-22-41 | D01758 | | | X1 | | | | TB0160Y | C016 | BJ | | 150-199, 275-299 |
| 051 | 22 | PA | | | 4-0 | 33-22-41 | D03558 | | | X1 | | | | D04290J | 10 | | | 050-099, 275-299 |
| 051 | 22 | PA | | | 5-0 | 33-22-41 | D10794 | | | B2 | | | | TB0146Y | A018 | BJ | | 150-199 |
| 052 | 22 | PA | | | 7-0 | 33-22-41 | D03558 | | | B2 | | | | TB0160Y | C016 | BJ | | 050-099 |
| 052 | 22 | PA | | | 5-0 | 33-22-41 | D03558 | | | B2 | | | | TB0160Y | C016 | BJ | | 150-199, 275-299 |
| 053 | 22 | PA | | | 4-0 | 33-22-41 | D03558 | | | B1 | | | | TB0174X | C002 | BJ | | ALL |
| 054 | 22 | PA | | | 3-0 | 33-22-41 | D10794 | | | C2 | | | | TB0146Z | 34 | BJ | | 050-099 |
| 054 | 22 | PA | | | 3-0 | 33-22-41 | D10794 | | | C2 | | | | TB0146Z | 33 | BJ | | 150-199, 275-299 |
| 055 | 20 | PA | | | 6-0 | 33-22-41 | D03558 | | | X2 | | | | GDX0002 | A.. | 2 | | 050-099 |
| 055 | 20 | PA | | | 5-0 | 33-22-41 | D03558 | | | X2 | | | | GDX0002 | A.. | 2 | | 150-199, 275-299 |
| 056 | 22 | PA | | | 4-0 | 33-24-11 | D05170J | | | 19 | | | | D03560 | D2 | | | 050-099 |
| 056 | 20 | PA | | | 4-0 | 33-24-11 | D05170J | | | 19 | | | | D03560 | D2 | | | 150-199, 275-299 |
| 057 | 22 | PA | | | 4-0 | 21-61-41 | D05088J | | | 46 | | | | D05138J | 16 | | | ALL |
| 059 | 22 | PA | | | 3-0 | 33-51-11 | D06410J | | | 4 | | | | TB0146Z | 39 | BJ | | 050-099 |
| 059 | 22 | PA | | | 2-0 | 33-51-11 | D06410J | | | 4 | | | | TB0146Z | 39 | BJ | | 150-199, 275-299 |
| 060 | 22 | PA | | | 4-0 | 33-51-11 | D06410J | | | 3 | | | | TB0160Y | A014 | BJ | | 050-099 |
| 060 | 22 | PA | | | 3-0 | 33-51-11 | D06410J | | | 3 | | | | TB0160Y | A014 | BJ | | 150-199, 275-299 |
| 061 | 22 | PA | | | 4-0 | 33-24-11 | D05170J | | | 21 | | | | D02254 | C2 | | | 050-099 |
| 061 | 20 | PA | | | 4-0 | 33-24-11 | D05170J | | | 21 | | | | D02254 | C2 | | | 150-199, 275-299 |
| 062 | 22 | PA | | | 4-0 | 33-24-11 | D03560 | | | B2 | | | | D05170J | 22 | | | ALL |
| 063 | 22 | PA | | | 3-0 | 33-24-11 | TB0146Y | | A015 | | BJ | | | D05170J | 20 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 063 | 20 | | PA | | 3-0 | 33-24-11 | TB0146Y | A015 | BJ | | D05170J | 20 | | | 150-199, 275-299 |
| 065 | 24 | | PK | | 5-0 | 33-24-11 | TB0146H | 22 | 2 | | D03560 | X1 | | | ALL |
| 066 | 24 | | PK | | 4-0 | 33-24-11 | TB0146Y | C015 | BJ | | D03560 | X2 | | | ALL |
| 067 | 20 | | PA | | 3-0 | 26-13-12 | D05170J | 43 | | | TB0174Y | A042 | BJ | | 162-199 |
| 068 | 22 | | PA | | 4-0 | 33-24-11 | TB0174Z | 36 | BJ | | D03560 | C1 | | | 050-099 |
| 068 | 22 | | PA | | 5-0 | 33-24-11 | TB0146Z | 13 | BJ | | D03560 | C1 | | | 150-199 |
| 068 | 20 | | PA | | 5-0 | 33-24-11 | D05162J | 4 | | | TB0174Z | 37 | BJ | | 275-299 |
| 069 | 22 | | PA | | 4-0 | 33-24-11 | TB0146Z | 20 | BJ | | D05166J | 4 | | | 050-099 |
| 069 | 20 | | PA | | 3-0 | 33-24-11 | TB0146Z | 20 | BJ | | D05166J | 4 | | | 150-199, 275-299 |
| 070 | 22 | | PA | | 4-0 | 33-24-11 | TB0146Z | 19 | BJ | | D05166J | 7 | | | 050-099 |
| 070 | 20 | | PA | | 3-0 | 33-24-11 | TB0146Z | 19 | BJ | | D05166J | 7 | | | 150-199, 275-299 |
| 071 | 22 | | PA | | 5-0 | 33-24-11 | TB0146Z | 13 | BJ | | D05162J | 4 | | | 150-199 |
| 072 | 22 | | PA | | 4-0 | 33-24-11 | TB0146Z | 14 | BJ | | D05162J | 7 | | | 150-199 |
| 072 | 20 | | PA | | 6-0 | 33-24-11 | TB0174Z | 38 | BJ | | D05162J | 7 | | | 275-299 |
| 073 | 24 | | PK | | 3-0 | 33-24-11 | TB0146Y | C015 | BJ | | D05088J | 11 | | | ALL |
| 075 | 24 | | PK | | 3-0 | 33-24-11 | TB0146Y | A016 | BJ | | D05088J | 14 | | | ALL |
| 076 | 22 | | PA | | 4-0 | 33-24-11 | TB0146Z | 20 | BJ | | D03560 | D1 | | | 050-099 |
| 076 | 20 | | PA | | 5-0 | 33-24-11 | TB0146Z | 20 | BJ | | D03560 | D1 | | | 150-199, 275-299 |
| 077 | 22 | | PA | | 4-0 | 33-24-11 | TB0146Z | 20 | BJ | | D05182J | 4 | | | 050-099 |
| 077 | 20 | | PA | | 3-0 | 33-24-11 | TB0146Z | 20 | BJ | | D05182J | 4 | | | 150-199, 275-299 |
| 078 | 22 | | PA | | 4-0 | 33-24-11 | TB0146Z | 19 | BJ | | D05182J | 7 | | | 050-099 |
| 078 | 20 | | PA | | 3-0 | 33-24-11 | TB0146Z | 19 | BJ | | D05182J | 7 | | | 150-199, 275-299 |
| 079 | 24 | | PK | | 5-0 | 33-24-11 | TB0146Y | C015 | BJ | | D02256 | D1 | | | ALL |
| 081 | 22 | | PA | | 5-0 | 33-24-11 | TB0146Y | A015 | BJ | | D03560 | C2 | | | 050-099 |
| 081 | 20 | | PA | | 5-0 | 33-24-11 | TB0146Y | A015 | BJ | | D03560 | C2 | | | 150-199, 275-299 |
| 082 | 22 | | PA | | 5-0 | 33-24-11 | TB0146Y | A015 | BJ | | D02254 | D2 | | | 050-099 |
| 082 | 20 | | PA | | 5-0 | 33-24-11 | TB0146Y | A015 | BJ | | D02254 | D2 | | | 150-199, 275-299 |
| 083 | 24 | | PK | | 5-0 | 33-24-11 | TB0146H | 22 | 2 | | D02254 | X1 | | | ALL |
| 084 | 24 | | PK | | 5-0 | 33-24-11 | TB0146Y | A016 | BJ | | D02254 | X2 | | | ALL |
| 085 | 22 | | PA | | 5-0 | 33-24-11 | D02254 | C1 | | | TB0146Z | 19 | BJ | | 050-099 |
| 085 | 20 | | PA | | 5-0 | 33-24-11 | D02254 | C1 | | | TB0146Z | 19 | BJ | | 150-199, 275-299 |
| 086 | 22 | | PA | | 3-0 | 33-24-11 | D04290J | 21 | | | TB0146Z | 20 | BJ | | 050-099 |
| 086 | 20 | | PA | | 3-0 | 33-24-11 | D04290J | 21 | | | TB0146Z | 20 | BJ | | 150-199, 275-299 |
| 087 | 22 | | PA | | 3-0 | 33-24-11 | D04290J | 20 | | | TB0146Z | 19 | BJ | | 050-099 |
| 087 | 20 | | PA | | 3-0 | 33-24-11 | D04290J | 20 | | | TB0146Z | 19 | BJ | | 150-199, 275-299 |
| 088 | 22 | | PA | | 5-0 | 33-24-11 | D02254 | D1 | | | TB0146Z | 14 | BJ | | 150-199 |
| 089 | 22 | | PA | | 2-0 | 33-24-11 | D03560 | B1 | | | D02256 | C3 | | | ALL |
| 090 | 24 | | PK | | 5-0 | 33-24-11 | TB0146Y | A016 | BJ | | D02256 | B2 | | | ALL |
| 091 | 22 | | PA | | 5-0 | 33-24-11 | TB0146Y | C016 | BJ | | D02256 | C2 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | |
| 092 | 24 | | PK | 5-0 | 33-24-11 | TB0146Y | A017 | BJ | | D02256 | D2 | | | ALL | | |
| 093 | 24 | | PK | 5-0 | 33-24-11 | TB0146H | 22 | 2 | | D02256 | X1 | | | ALL | | |
| 094 | 24 | | PK | 4-0 | 33-24-11 | D05170J | 23 | | | D02256 | X2 | | | ALL | | |
| 095 | 20 | | PA | 3-0 | 33-24-11 | GDY0001 | D.. | 2 | | TB0146Y | A017 | BJ | | ALL | | |
| 096 | 24 | | PK | 5-0 | 33-24-11 | D02256 | B1 | | | TB0146Y | A017 | BJ | | ALL | | |
| 097 | 22 | | PA | 4-0 | 21-61-31 | D05088J | | 3 | | D05148J | 4 | | | ALL | | |
| 098 | 22 | | PA | 3-0 | 33-25-11 | D05090J | | 5 | | TB0146Y | C017 | BJ | | 050-099 | | |
| 099 | 20 | | PA | 3-0 | 33-26-21 | D05088J | | 15 | | TB0146Z | 35 | BJ | | 050-099, 150-199 | | |
| 099 | 20 | | PA | 3-0 | 33-26-21 | D05088J | | 15 | | TB0146Y | A028 | BJ | | 275-299 | | |
| 100 | 20 | | PA | 3-0 | 33-27-11 | D05170J | | 31 | | TB0174Z | 29 | BJ | | ALL | | |
| 101 | 22 | | PA | 4-0 | 33-27-11 | D05148J | | 19 | | TB0174Z | 29 | BJ | | ALL | | |
| 104 | 20 | | PA | 3-0 | 33-51-11 | D06412J | | 2 | | TB0160H | 1 | 2 | | 050-099 | | |
| 104 | 20 | | PA | 2-0 | 33-51-11 | D06412J | | 2 | | TB0160H | 1 | 2 | | 150-199, 275-299 | | |
| 105 | 22 | | PA | 3-0 | 33-26-11 | D05088J | | 20 | | TB0146Y | C006 | BJ | | ALL | | |
| 106 | 22 | | PA | 3-0 | 33-51-11 | D06412J | | 8 | | TB0160Z | 10 | BJ | | 050-099 | | |
| 106 | 22 | | PA | 2-0 | 33-51-11 | D06412J | | 8 | | TB0160Z | 10 | BJ | | 150-199, 275-299 | | |
| 107 | 22 | | PA | 3-0 | 33-51-11 | D06412J | | 4 | | TB0146Z | 39 | BJ | | 050-099 | | |
| 107 | 22 | | PA | 2-0 | 33-51-11 | D06412J | | 4 | | TB0146Z | 39 | BJ | | 150-199, 275-299 | | |
| 108 | 20 | | PA | 4-0 | 33-41-11 | D05088J | | 31 | | D05082J | 3 | | | 050-099 | | |
| 108 | 18 | | PA | 4-0 | 33-41-11 | D05088J | | 31 | DL | D05082J | 3 | DK | | 150-199, 275-299 | | |
| 109 | 20 | | PA | 4-0 | 33-41-11 | D05088J | | 32 | | D05076J | 1 | | | 050-099 | | |
| 109 | 18 | | PA | 4-0 | 33-41-11 | D05088J | | 32 | DL | D05076J | 1 | DK | | 150-199, 275-299 | | |
| 110 | 22 | | PA | 3-0 | 33-51-11 | D06412J | | 3 | | TB0160Y | A015 | BJ | | 050-099 | | |
| 110 | 22 | | PA | 2-0 | 33-51-11 | D06412J | | 3 | | TB0160Y | A015 | BJ | | 150-199 | | |
| 110 | 22 | | PA | 3-0 | 33-51-11 | D06412J | | 3 | | TB0160Y | C014 | BJ | | 275-299 | | |
| 111 | 20 | | PA | 3-0 | 33-51-11 | D05088J | | 21 | | TB0174X | C019 | BJ | | ALL | | |
| 112 | 20 | | PA | 4-0 | 33-51-11 | D05076J | | 2 | | TB0160H | 1 | 2 | | 050-099 | | |
| 112 | 20 | | PA | 3-0 | 33-51-11 | D05076J | | 2 | | TB0160H | 1 | 2 | | 150-199, 275-299 | | |
| 113 | 20 | | PA | 5-0 | 33-51-11 | D05088J | | 24 | | TB0160H | 1 | 2 | | 050-099 | | |
| 113 | 20 | | PA | 3-0 | 33-51-11 | D05088J | | 24 | | TB0160H | 1 | 2 | | 150-199, 275-299 | | |
| 114 | 20 | | PA | 3-0 | 33-51-11 | D05088J | | 23 | | TB0174X | D019 | BJ | | ALL | | |
| 115 | 20 | | PA | 4-0 | 33-51-11 | D05076J | | 3 | | TB0160G | 37 | 2 | | 050-099 | | |
| 115 | 20 | | PA | 3-0 | 33-51-11 | D05076J | | 3 | | TB0160G | 37 | 2 | | 150-199, 275-299 | | |
| 116 | 20 | | PA | 4-0 | 33-51-11 | D05076J | | 4 | | TB0160G | 37 | 2 | | 050-099 | | |
| 116 | 20 | | PA | 3-0 | 33-51-11 | D05076J | | 4 | | TB0160G | 37 | 2 | | 150-199, 275-299 | | |
| 117 | 22 | | PA | 5-0 | 33-51-11 | D05088J | | 25 | | TB0160Z | 11 | BJ | | 050-099 | | |
| 117 | 22 | | PA | 3-0 | 33-51-11 | D05088J | | 25 | | TB0160Z | 11 | BJ | | 150-199, 275-299 | | |
| 119 | 22 | | PA | 5-0 | 33-51-11 | D05088J | | 27 | | TB0160Z | 10 | BJ | | 050-099 | | |
| 119 | 22 | | PA | 3-0 | 33-51-11 | D05088J | | 27 | | TB0160Z | 10 | BJ | | 150-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 120 | 22 | | PA | | 4-0 | 33-51-11 | D05076J | | 5 | | TB0146Z | 39 | BJ | | 050-099 |
| 120 | 22 | | PA | | 3-0 | 33-51-11 | D05076J | | 5 | | TB0146Z | 39 | BJ | | 150-199, 275-299 |
| 121 | 22 | | PA | | 5-0 | 33-51-11 | D05076J | | 6 | | TB0160Z | 11 | BJ | | 050-099 |
| 121 | 22 | | PA | | 3-0 | 33-51-11 | D05076J | | 6 | | TB0160Z | 11 | BJ | | 150-199, 275-299 |
| 122 | 22 | | PA | | 5-0 | 33-51-11 | D05088J | | 28 | | TB0146Z | 39 | BJ | | 050-099 |
| 122 | 22 | | PA | | 3-0 | 33-51-11 | D05088J | | 28 | | TB0146Z | 39 | BJ | | 150-199, 275-299 |
| 126 | 22 | | PA | | 3-0 | 33-51-11 | D05088J | | 30 | | D04290J | 39 | | | ALL |
| 128 | 22 | | PA | | 3-0 | 33-51-11 | TB0160Z | 11 | BJ | | TB0146Z | 39 | BJ | | ALL |
| 133 | 22 | | PA | | 3-0 | 33-51-11 | TB0160Z | 10 | BJ | | D05076J | 12 | | | ALL |
| 137 | 22 | | PA | | 5-0 | 33-51-11 | TB0160Z | 10 | BJ | | D04290J | 27 | | | 050-099 |
| 137 | 22 | | PA | | 3-0 | 33-51-11 | TB0160Z | 10 | BJ | | D04290J | 27 | | | 150-199, 275-299 |
| 139 | 22 | | PA | | 4-0 | 33-51-21 | TB0160Y | A012 | BJ | | D05082J | 6 | | | ALL |
| 140 | 20 | | PA | | 4-0 | 33-51-21 | TB0160Y | C012 | BJ | | D05082J | 7 | | | 050-099 |
| 140 | 20 | | PA | | 3-0 | 33-51-21 | TB0160Y | C012 | BJ | | D05082J | 7 | | | 150-199, 275-299 |
| 141 | 20 | | PA | | 8-0 | 33-51-21 | TB0160Y | C012 | BJ | | D03572 | A3 | | | 050-099 |
| 141 | 20 | | PA | | 4-0 | 33-51-21 | TB0160Y | C012 | BJ | | D03572 | A3 | | | 150-199, 275-299 |
| 142 | 20 | | PA | | 4-0 | 33-51-21 | TB0146Z | 40 | BJ | | D03572 | A2 | | | ALL |
| 143 | 20 | | PA | | 4-0 | 33-51-21 | TB0146Z | 40 | BJ | | D03572 | X1 | | | ALL |
| 144 | 20 | | PA | | 4-0 | 33-51-21 | D05090J | 12 | | | D03572 | X2 | | | ALL |
| 145 | 20 | | PA | | 4-0 | 33-51-21 | D05090J | 13 | | | D03574 | X2 | | | ALL |
| 146 | 20 | | PA | | 8-0 | 33-51-21 | TB0160H | 3 | 2 | | D03574 | X1 | | | 050-099 |
| 146 | 20 | | PA | | 5-0 | 33-51-21 | TB0160H | 3 | 2 | | D03574 | X1 | | | 150-199, 275-299 |
| 147 | 20 | | PA | | 8-0 | 33-51-21 | TB0160H | 3 | 2 | | D03574 | A2 | | | 050-099 |
| 147 | 20 | | PA | | 5-0 | 33-51-21 | TB0160H | 3 | 2 | | D03574 | A2 | | | 150-199, 275-299 |
| 148 | 20 | | PA | | 8-0 | 33-51-21 | TB0160Y | A013 | BJ | | D03574 | A3 | | | 050-099 |
| 148 | 20 | | PA | | 5-0 | 33-51-21 | TB0160Y | A013 | BJ | | D03574 | A3 | | | 150-199, 275-299 |
| 152 | 22 | | PA | | 3-0 | 33-51-21 | TB0160Y | A012 | BJ | | D05082J | 22 | | | ALL |
| 153 | 20 | | PA | | 3-0 | 33-51-21 | TB0160Y | C012 | BJ | | D05082J | 23 | | | ALL |
| 154 | 20 | | PA | | 4-0 | 33-51-21 | TB0160Y | A013 | BJ | | D05076J | 16 | | | 050-099 |
| 154 | 20 | | PA | | 3-0 | 33-51-21 | TB0160Y | A013 | BJ | | D05076J | 16 | | | 150-199, 275-299 |
| 155 | 22 | | PA | | 4-0 | 33-51-21 | TB0160Y | C013 | BJ | | D05076J | 17 | | | 050-099 |
| 155 | 22 | | PA | | 3-0 | 33-51-21 | TB0160Y | C013 | BJ | | D05076J | 17 | | | 150-199, 275-299 |
| 157 | 22 | | PA | | 3-0 | 33-51-21 | TB0160Z | 11 | BJ | | D05076J | 19 | | | ALL |
| 158 | 20 | | PA | | 4-0 | 33-51-21 | TB0160Y | A013 | BJ | | D05076J | 20 | | | 050-099 |
| 158 | 20 | | PA | | 3-0 | 33-51-21 | TB0160Y | A013 | BJ | | D05076J | 20 | | | 150-199, 275-299 |
| 159 | 22 | | PA | | 4-0 | 33-51-21 | TB0160Y | C013 | BJ | | D05076J | 21 | | | 050-099 |
| 159 | 22 | | PA | | 3-0 | 33-51-21 | TB0160Y | C013 | BJ | | D05076J | 21 | | | 150-199, 275-299 |
| 160 | 22 | | PA | | 4-0 | 52-11-11 | D03606 | | A2 | | D05170J | 28 | | | ALL |
| 161 | 22 | | PA | | 4-0 | 52-11-11 | D03606 | | B2 | | D05170J | 29 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | | |
| 162 | 22 | | PA | | 4-0 | 52-11-11 | D03606 | | | | C2 | | | D05170J | 30 | | | ALL |
| 163 | 22 | | PA | | 2-0 | 52-11-11 | D03606 | | | | A3 | | | D03604 | A1 | | | 050-099 |
| 163 | 22 | | PA | | 1-0 | 52-11-11 | D03606 | | | | A3 | | | D03604 | A1 | | | 150-199, 275-299 |
| 164 | 22 | | PA | | 2-0 | 52-11-11 | D03606 | | | | A1 | | | D03604 | B3 | | | 050-099 |
| 164 | 22 | | PA | | 1-0 | 52-11-11 | D03606 | | | | A1 | | | D03604 | B3 | | | 150-199, 275-299 |
| 165 | 22 | | PA | | 2-0 | 52-11-11 | D03606 | | | | B3 | | | D03604 | B1 | | | 050-099 |
| 165 | 22 | | PA | | 1-0 | 52-11-11 | D03606 | | | | B3 | | | D03604 | B1 | | | 150-199, 275-299 |
| 166 | 22 | | PA | | 2-0 | 52-11-11 | D03606 | | | | B1 | | | D03604 | A3 | | | 050-099 |
| 166 | 22 | | PA | | 1-0 | 52-11-11 | D03606 | | | | B1 | | | D03604 | A3 | | | 150-199, 275-299 |
| 167 | 22 | | PA | | 2-0 | 52-11-11 | D03606 | | | | C3 | | | D03604 | C1 | | | 050-099 |
| 167 | 22 | | PA | | 1-0 | 52-11-11 | D03606 | | | | C3 | | | D03604 | C1 | | | 150-199, 275-299 |
| 168 | 22 | | PA | | 2-0 | 52-11-11 | D03606 | | | | C1 | | | D03604 | C3 | | | 050-099 |
| 168 | 22 | | PA | | 1-0 | 52-11-11 | D03606 | | | | C1 | | | D03604 | C3 | | | 150-199, 275-299 |
| 169 | 22 | | PA | | 4-0 | 52-11-11 | D03604 | | | | A2 | | | D04290J | 2 | | | ALL |
| 170 | 22 | | PA | | 4-0 | 52-11-11 | D03604 | | | | B2 | | | D04290J | 30 | | | ALL |
| 171 | 22 | | PA | | 4-0 | 52-11-11 | D03604 | | | | C2 | | | D04290J | 31 | | | ALL |
| 176 | 22 | | PA | | 5-0 | 52-11-12 | M01152 | | | | A | C | | TB0174Y | A017 | BJ | | ALL |
| 177 | 22 | | PA | | 7-0 | 52-11-12 | D03602 | | | | B3 | | | M01152 | B | C | | ALL |
| 178 | 22 | | PA | | 3-0 | 52-11-12 | D04290J | | | | 1 | | | TB0174Y | C016 | BJ | | ALL |
| 179 | 22 | | PA | | 4-0 | 52-11-12 | D03602 | | | | X1 | | | TB0174Y | C016 | BJ | | ALL |
| 180 | 22 | | PA | | 3-0 | 52-11-12 | D05090J | | | | 16 | | | TB0174Y | A016 | BJ | | ALL |
| 181 | 22 | | PA | | 4-0 | 52-11-12 | D03602 | | | | X2 | | | TB0174Y | A016 | BJ | | ALL |
| 182 | 22 | | PA | | 4-0 | 52-11-12 | D03602 | | | | A1 | | | TB0174Y | A016 | BJ | | ALL |
| 183 | 22 | | PA | | 4-0 | 52-11-12 | D03602 | | | | A3 | | | D05090J | 14 | | | ALL |
| 184 | 22 | | PA | | 3-0 | 52-11-12 | D10468 | | | | A2 | | | D04290J | 32 | | | ALL |
| 185 | 22 | | PA | | 3-0 | 52-11-12 | D10468 | | | | A1 | | | D03602 | B1 | | | ALL |
| 186 | 22 | | PA | | 3-0 | 52-11-12 | D04290J | | | | 12 | | | TB0174Y | C015 | BJ | | 050-099, 275-299 |
| 186 | 22 | | PA | | 3-0 | 52-11-12 | TB0174Y | | | | C015 | BJ | | D04290J | 12 | | | 150-199 |
| 187 | 22 | | PA | | 3-0 | 52-11-12 | D10468 | | | | B2 | | | TB0174Y | C015 | BJ | | ALL |
| 188 | 22 | | PA | | 3-0 | 52-11-12 | D10468 | | | | B1 | | | TB0174Y | C016 | BJ | | ALL |
| 189 | 22 | | PA | | 3-0 | 52-11-12 | D10468 | | | | X1 | | | TB0174Y | C015 | BJ | | ALL |
| 190 | 22 | | PA | | 3-0 | 52-11-12 | D10468 | | | | X2 | | | TB0174Y | A016 | BJ | | ALL |
| 191 | 22 | | PA | | 4-0 | 52-11-12 | D03606 | | | | X1 | | | TB0174Y | A017 | BJ | | ALL |
| 192 | 22 | | PA | | 4-0 | 52-11-12 | D03606 | | | | X2 | | | D05090J | 15 | | | ALL |
| 193 | 22 | | PA | | 2-0 | 52-11-12 | D03604 | | | | X2 | | | D03602 | A2 | | | ALL |
| 194 | 22 | | PA | | 2-0 | 52-11-12 | D03604 | | | | X1 | | | D03602 | B2 | | | ALL |
| 195 | 22 | | PA | | 3-0 | 52-11-12 | D04290J | | | | 36 | | | TB0174Y | A015 | BJ | | 050-099, 150-199 |
| 195 | 20 | | PA | | 3-0 | 52-11-12 | D04290J | | | | 36 | | | TB0174Y | A015 | BJ | | 275-299 |
| 196 | 24 | | PK | | 3-0 | 52-11-12 | D05090J | | | | 17 | | | TB0174Y | A015 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 197 | 22 | PA | | 3-0 | 52-11-12 | D04290J | 33 | | | | TB0174Y | A017 | BJ | | ALL |
| 198 | 22 | PA | | 3-0 | 52-11-12 | D04290J | 34 | | | | TB0174Y | A015 | BJ | | ALL |
| 199 | 22 | PA | | 4-0 | 33-21-21 | S00800 | 2 | C | * | | D05148J | 3 | | | 275-299 |
| 201B | 22 | PB | A | 4-0 | 21-51-22 | D05082J | 1 | | | | D05090J | 8 | | | ALL |
| 201R | 22 | PB | A | 0-0 | 21-51-22 | D05082J | 2 | | | | D05090J | 9 | | | ALL |
| 202B | 24 | PL | B | 4-0 | 21-61-31 | D05082J | 4 | | | | D05090J | 10 | | | ALL |
| 202R | 24 | PL | B | 0-0 | 21-61-31 | D05082J | 5 | | | | D05090J | 11 | | | ALL |
| 203B | 20 | PB | C | 4-0 | 21-65-11 | D05088J | 5 | | | | D05138J | 10 | | | ALL |
| 203R | 20 | PB | C | 0-0 | 21-65-11 | D05088J | 6 | | | | D05138J | 11 | | | ALL |
| 204B | 20 | PB | D | 4-0 | 21-65-11 | D05088J | 7 | | | | D05138J | 12 | | | ALL |
| 204R | 20 | PB | D | 0-0 | 21-65-11 | D05088J | 8 | | | | D05138J | 13 | | | ALL |
| 205B | 20 | PB | E | 4-0 | 21-65-11 | D05088J | 9 | | | | D05148J | 7 | | | ALL |
| 205R | 20 | PB | E | 0-0 | 21-65-11 | D05088J | 10 | | | | D05148J | 13 | | | ALL |
| 206B | 24 | PL | F | 5-0 | 52-71-11 | D05090J | 23 | | | | D05076J | 23 | | | ALL |
| 206R | 24 | PL | F | 0-0 | 52-71-11 | D05090J | 22 | | | | D05076J | 22 | | | ALL |
| 207B | 24 | PL | G | 5-0 | 52-71-11 | D05090J | 25 | | | | D05076J | 25 | | | ALL |
| 207R | 24 | PL | G | 0-0 | 52-71-11 | D05090J | 24 | | | | D05076J | 24 | | | ALL |
| 208B | 24 | PL | H | 5-0 | 52-71-11 | D05090J | 27 | | | | D05076J | 27 | | | ALL |
| 208R | 24 | PL | H | 0-0 | 52-71-11 | D05090J | 26 | | | | D05076J | 26 | | | ALL |
| 209B | 24 | PL | I | 5-0 | 52-71-11 | D05090J | 29 | | | | D05076J | 29 | | | ALL |
| 209R | 24 | PL | I | 0-0 | 52-71-11 | D05090J | 28 | | | | D05076J | 28 | | | ALL |
| 210B | 24 | PL | J | 5-0 | 52-71-11 | D05076J | 33 | | | | D05090J | 37 | | | ALL |
| 210R | 24 | PL | J | 0-0 | 52-71-11 | D05076J | 32 | | | | D05090J | 36 | | | ALL |
| 211B | 24 | PL | K | 5-0 | 52-71-11 | D05076J | 35 | | | | D05090J | 39 | | | ALL |
| 211R | 24 | PL | K | 0-0 | 52-71-11 | D05076J | 34 | | | | D05090J | 38 | | | ALL |
| 212B | 22 | PB | L | 4-0 | 23-31-14 | D05138J | 7 | | | | TB0174Z | 24 | BJ | | 275-299 |
| 212R | 22 | PB | L | 0-0 | 23-31-14 | D05138J | 6 | | | | TB0174Z | 23 | BJ | | 275-299 |
| 213B | 22 | PB | M | 4-0 | 23-31-14 | D05166J | 2 | | | | TB0174Z | 24 | BJ | | ALL |
| 213R | 22 | PB | M | 0-0 | 23-31-14 | D05166J | 1 | | | | TB0174Z | 23 | BJ | | ALL |
| 214B | 22 | PB | N | 4-0 | 23-31-14 | D05162J | 2 | | | | TB0174Z | 24 | BJ | | ALL |
| 214R | 22 | PB | N | 0-0 | 23-31-14 | D05162J | 1 | | | | TB0174Z | 23 | BJ | | ALL |
| 215B | 22 | PB | O | 4-0 | 23-31-14 | D05182J | 2 | | | | TB0174Z | 24 | BJ | | ALL |
| 215R | 22 | PB | O | 0-0 | 23-31-14 | D05182J | 1 | | | | TB0174Z | 23 | BJ | | ALL |
| 216B | 22 | PB | P | 3-0 | 23-31-14 | D05170J | 18 | | | | TB0174Z | 24 | BJ | | 050-099, 150-199 |
| 216B | 22 | PB | P | 2-0 | 23-31-14 | TB0174Y | C025 | BJ | | | TB0174Z | 24 | BJ | | 275-299 |
| 216R | 22 | PB | P | 0-0 | 23-31-14 | D05170J | 17 | | | | TB0174Z | 23 | BJ | | 050-099, 150-199 |
| 216R | 22 | PB | P | 0-0 | 23-31-14 | TB0174Y | A025 | BJ | | | TB0174Z | 23 | BJ | | 275-299 |
| 217B | 22 | PB | Q | 3-0 | 23-31-14 | D05090J | 48 | | | | TB0174Z | 24 | BJ | | 050-099, 150-199 |
| 217B | 22 | PB | Q | 3-0 | 23-31-14 | D05090J | 7 | | | | TB0174Z | 24 | BJ | | 275-299 |

WIRE LIST

D280T132

91-21-11
 Section W1060
 Page 8
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 217R | 22 | PB | Q | 0-0 | 23-31-14 | D05090J | | 47 | | | | | TB0174Z | 23 | BJ | | 050-099, 150-199 |
| 217R | 22 | PB | Q | 0-0 | 23-31-14 | D05090J | | 6 | | | | | TB0174Z | 23 | BJ | | 275-299 |
| 218B | 24 | PL | R | 4-0 | 52-71-12 | D05090J | | 31 | | | | | D05082J | 11 | | | ALL |
| 218R | 24 | PL | R | 0-0 | 52-71-12 | D05090J | | 30 | | | | | D05082J | 10 | | | ALL |
| 219B | 24 | PL | S | 5-0 | 52-71-12 | D05090J | | 33 | | | | | D05076J | 31 | | | ALL |
| 219R | 24 | PL | S | 0-0 | 52-71-12 | D05090J | | 32 | | | | | D05076J | 30 | | | ALL |
| 220B | 22 | PB | T | 3-0 | 23-31-14 | D05090J | | 7 | | | | | TB0174Z | 34 | BJ | | 050-099, 150-199 |
| 220R | 22 | PB | T | 0-0 | 23-31-14 | D05090J | | 6 | | | | | TB0174Z | 33 | BJ | | 050-099, 150-199 |
| 221B | 22 | PB | U | 4-0 | 23-31-14 | D05166J | | 5 | | | | | TB0174Z | 34 | BJ | | 050-099, 150-199 |
| 221R | 22 | PB | U | 0-0 | 23-31-14 | D05166J | | 6 | | | | | TB0174Z | 33 | BJ | | 050-099, 150-199 |
| 222B | 22 | PB | V | 4-0 | 23-31-14 | D05162J | | 5 | | | | | TB0174Z | 34 | BJ | | 050-099, 150-199 |
| 222R | 22 | PB | V | 0-0 | 23-31-14 | D05162J | | 6 | | | | | TB0174Z | 33 | BJ | | 050-099, 150-199 |
| 223B | 22 | PB | W | 4-0 | 23-31-14 | D05182J | | 5 | | | | | TB0174Z | 34 | BJ | | 050-099 |
| 223B | 22 | PB | W | 5-0 | 23-31-14 | D05182J | | 5 | | | | | TB0174Z | 34 | BJ | | 150-199 |
| 223R | 22 | PB | W | 0-0 | 23-31-14 | D05182J | | 6 | | | | | TB0174Z | 33 | BJ | | 050-099, 150-199 |
| 228B | 24 | PL | AB | 5-0 | 52-71-12 | D05090J | | 21 | | | | | D05082J | 26 | | | 150-199, 275-299 |
| 228R | 24 | PL | AB | 0-0 | 52-71-12 | D05090J | | 20 | | | | | D05082J | 25 | | | 150-199, 275-299 |
| 229B | 24 | PL | AC | 5-0 | 52-71-12 | D05090J | | 35 | | | | | D05076J | 39 | | | 150-199, 275-299 |
| 229R | 24 | PL | AC | 0-0 | 52-71-12 | D05090J | | 34 | | | | | D05076J | 38 | | | 150-199, 275-299 |
| 230B | 24 | PL | AD | 4-0 | 21-61-41 | D05090J | | 52 | | | | | D05138J | 18 | | | ALL |
| 230R | 24 | PL | AD | 0-0 | 21-61-41 | D05090J | | 51 | | | | | D05138J | 17 | | | ALL |
| 231B | 24 | PL | AE | 4-0 | 21-61-41 | D05090J | | 54 | | | | | D05138J | 20 | | | ALL |
| 231R | 24 | PL | AE | 0-0 | 21-61-41 | D05090J | | 53 | | | | | D05138J | 19 | | | ALL |
| 232B | 24 | PL | AF | 4-0 | 21-61-31 | D05090J | | 40 | | | | | D05148J | 21 | | | ALL |
| 232R | 24 | PL | AF | 0-0 | 21-61-31 | D05090J | | 41 | | | | | D05148J | 23 | | | ALL |
| 233B | 20 | PB | AG | 4-0 | 21-65-11 | D05088J | | 49 | | | | | D05138J | 23 | | | ALL |
| 233R | 20 | PB | AG | 0-0 | 21-65-11 | D05088J | | 50 | | | | | D05138J | 24 | | | ALL |
| 234B | 20 | PB | AH | 4-0 | 21-65-11 | D05088J | | 47 | | | | | D05138J | 21 | | | ALL |
| 234R | 20 | PB | AH | 0-0 | 21-65-11 | D05088J | | 48 | | | | | D05138J | 22 | | | ALL |
| 236B | 22 | PB | AJ | 3-0 | 23-31-14 | TB0174Y | | | C025 | | BJ | | D05170J | 18 | | | 275-299 |
| 236R | 22 | PB | AJ | 0-0 | 23-31-14 | TB0174Y | | | A025 | | BJ | | D05170J | 17 | | | 275-299 |
| 238B | 22 | PB | AL | 5-0 | 23-31-14 | D05090J | | 46 | | | | | D05182J | 9 | | | 050-099, 150-199 |
| 238R | 22 | PB | AL | 0-0 | 23-31-14 | D05090J | | 45 | | | | | D05182J | 8 | | | 050-099, 150-199 |
| 244B | 22 | PR | JS | 4-0 | 21-66-21 | D05148J | | 39 | | | | | D05088J | 42 | | | 050-099 |
| 244B | 22 | PR | JS | 5-0 | 21-66-21 | D05088J | | 42 | | | | | D05148J | 39 | | | 162-199 |
| 244R | 22 | PR | JS | 0-0 | 21-66-21 | D05148J | | 38 | | | | | D05088J | 41 | | | 050-099 |
| 244R | 22 | PR | JS | 0-0 | 21-66-21 | D05088J | | 41 | | | | | D05148J | 38 | | | 162-199 |
| 244Z | | | JS | 0-0 | 21-66-21 | D05148J | | 37 | | | | | D05088J | 40 | | | 050-099 |
| 244Z | | | JS | 0-0 | 21-66-21 | D05088J | | 40 | | | | | D05148J | 37 | | | 162-199 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|-----------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 245B | 22 | PB | L | 4-0 | 23-31-14 | D05090J | 50 | | | D05138J | 7 | | | 050-099 | |
| 245B | 22 | PB | L | 5-0 | 23-31-14 | D05138J | 7 | | | D05090J | 50 | | | 150-199 | |
| 245R | 22 | PB | L | 0-0 | 23-31-14 | D05090J | 49 | | | D05138J | 6 | | | 050-099 | |
| 245R | 22 | PB | L | 0-0 | 23-31-14 | D05138J | 6 | | | D05090J | 49 | | | 150-199 | |
| 247B | 24 | PL | JV | 4-0 | 21-61-71 | D05148J | 32 | | | TB0160F | A025 | 2 | | 050-099 | |
| 247B | 24 | PL | JV | 5-0 | 21-61-71 | TB0160F | A025 | 2 | | D05148J | 32 | | | 150-199 | |
| 247B | 24 | PL | JV | 4-0 | 21-61-71 | TB0160F | A025 | 2 | | D05148J | 32 | | | 275-299 | |
| 247R | 24 | PL | JV | 0-0 | 21-61-71 | D05148J | 33 | | | TB0160F | C025 | 2 | | 050-099 | |
| 247R | 24 | PL | JV | 0-0 | 21-61-71 | TB0160F | C025 | 2 | | D05148J | 33 | | | 150-199, 275-299 | |
| 248B | 24 | PL | JW | 4-0 | 21-61-71 | D05082J | 29 | | | TB0160F | A027 | 2 | | 050-099 | |
| 248B | 24 | PL | JW | 3-0 | 21-61-71 | TB0160F | A027 | 2 | | D05082J | 29 | | | 150-199, 275-299 | |
| 248R | 24 | PL | JW | 0-0 | 21-61-71 | D05082J | 28 | | | TB0160F | C027 | 2 | | 050-099 | |
| 248R | 24 | PL | JW | 0-0 | 21-61-71 | TB0160F | C027 | 2 | | D05082J | 28 | | | 150-199, 275-299 | |
| 249B | 20 | PB | JX | 3-0 | 21-65-11 | D05148J | 18 | | | TB0160F | A021 | 2 | | 050-099 | |
| 249B | 20 | PB | JX | 4-0 | 21-65-11 | TB0160F | A021 | 2 | | D05148J | 18 | | | 150-199, 275-299 | |
| 249R | 20 | PB | JX | 0-0 | 21-65-11 | D05148J | 31 | | | TB0160F | C021 | 2 | | 050-099 | |
| 249R | 20 | PB | JX | 0-0 | 21-65-11 | TB0160F | C021 | 2 | | D05148J | 31 | | | 150-199, 275-299 | |
| 502 | 24 | PK | | 5-0 | 33-21-31 | D13358 | Y1 | | | TB0146Y | A032 | BJ | | 155-157, 166-199 | |
| 502 | 20 | PA | | 3-0 | 33-22-31 | D04290J | 3 | | | D05170J | 9 | | | 275-299 | |
| 503 | 20 | PA | | 4-0 | 33-22-42 | D05148J | 14 | | | D05170J | 16 | | | 050-099, 150-199 | |
| 503 | 20 | PA | | 6-0 | 33-22-42 | S01640 | 2 | C | | D05170J | 16 | | | 275-299 | |
| 504 | 22 | PA | | 4-0 | 33-27-11 | D04290J | 3 | | | TB0146X | C007 | BJ | | 050-099, 150-199 | |
| 504 | 22 | PA | | 3-0 | 33-27-11 | D05170J | 32 | | | TB0146X | C007 | BJ | | 275-299 | |
| 505 | 22 | PA | | 4-0 | 33-27-11 | D04290J | 11 | | | TB0146X | B008 | BJ | | 050-099, 150-199 | |
| 505 | 22 | PA | | 3-0 | 33-27-11 | D05170J | 33 | | | TB0146X | B008 | BJ | | 275-299 | |
| 506 | 22 | PA | | 5-0 | 23-31-11 | D03560 | A2 | | | TB0146H | 22 | 2 | | ALL | |
| 507 | 22 | PA | | 4-0 | 23-31-11 | D03560 | A1 | | | D05090J | 18 | | | 050-099, 151, 275-299 | |
| 508 | 22 | PA | | 5-0 | 23-31-11 | D02254 | A2 | | | TB0146H | 22 | 2 | | ALL | |
| 509 | 22 | PA | | 4-0 | 23-31-11 | D02254 | A1 | | | D05090J | 19 | | | ALL | |
| 510 | 22 | PA | | 6-0 | 25-65-12 | D05082J | 12 | | | D10736 | 3 | | | ALL | |
| 511 | 22 | PA | | 6-0 | 25-65-11 | D05082J | 13 | | | D10736 | 14 | | | ALL | |
| 512 | 24 | PK | | 2-0 | 24-51-51 | D05088J | 16 | | | D04290J | 22 | | | ALL | |
| 514 | 24 | PK | | 2-0 | 24-51-51 | D05088J | 18 | | | D04290J | 24 | | | ALL | |
| 515 | 24 | PK | | 2-0 | 24-51-51 | D05088J | 13 | | | D04290J | 25 | | | ALL | |
| 516 | 24 | PK | | 3-0 | 23-31-13 | TB0174G | 22 | 2 | | D04290J | 41 | | | ALL | |
| 517 | 22 | PA | | 3-0 | 33-22-32 | D04290J | 50 | | | TB0146Y | A018 | BJ | | 050-099 | |
| 517 | 22 | PA | | 4-0 | 33-22-32 | D04290J | 50 | | | TB0146Y | A018 | BJ | | 150-199 | |
| 518 | 22 | PA | | 3-0 | 33-22-41 | D05170J | 14 | | | TB0146Y | A018 | BJ | | 050-099 | |
| 518 | 22 | PA | | 4-0 | 33-22-41 | TB0146Y | A018 | BJ | | D05170J | 14 | | | 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 519 | 22 | | PA | 6-0 | 33-22-21 | D05170J | | 15 | | | | | D05076J | 36 | | | 050-099 |
| 519 | 22 | | PA | 5-0 | 33-22-21 | D05170J | | 15 | | | | | SMZ0001 | | S | | 150, 153-157 |
| 519 | 22 | | PA | 5-0 | 33-22-21 | D05170J | | 15 | | | | | D05076J | 36 | | | 151-152 |
| 519 | 22 | | PA | 3-0 | 33-22-21 | D05170J | | 15 | | | | | TB0146Y | A043 | BJ | | 280-299 |
| 520 | 20 | | PA | 3-0 | 33-26-11 | D05088J | | 19 | | | | | TB0146Z | 36 | BJ | | ALL |
| 522 | 24 | | PK | 6-0 | 33-21-11 | D04290J | | 29 | | | | | S01634 | 6 | C | | 275-299 |
| 524 | 22 | | PA | 4-0 | 33-51-11 | D04290J | | 37 | | | | | TB0160H | 1 | 2 | | ALL |
| 525 | 22 | | PA | 5-0 | 33-51-11 | D04290J | | 38 | | | | | TB0160Z | 11 | BJ | | 050-099 |
| 525 | 22 | | PA | 4-0 | 33-51-11 | D04290J | | 38 | | | | | TB0160Z | 11 | BJ | | 150-199, 275-299 |
| 526 | 20 | | PA | 3-0 | 33-21-11 | D05088J | | 1 | | | | | TB0174Z | 28 | BJ | | 050-099 |
| 528 | 24 | | PK | 5-0 | 33-21-31 | D13358 | | X1 | | | | | TB0146Y | A032 | BJ | | 155-157, 166-199 |
| 528 | 20 | | PA | 3-0 | 33-22-11 | D04290J | | 13 | | | | | TB0146G | 32 | 2 | | 275-278 |
| 528 | 20 | | PA | 4-0 | 33-22-11 | D04290J | | 13 | | | | | TB0146H | 1 | 2 | | 280-299 |
| 532 | 20 | | PA | 2-0 | 33-21-31 | TB0146Y | | | A032 | BJ | | | TB0174Z | 28 | BJ | | 050-099 |
| 534 | 24 | | PK | 3-0 | 31-31-26 | D04290J | | 35 | | | | | TB0146Z | 20 | BJ | | 050-099 |
| 534 | 24 | | PK | 4-0 | 31-31-26 | D04290J | | 35 | | | | | TB0146Z | 20 | BJ | | 150-199, 275-299 |
| 535 | 24 | | PK | 5-0 | 33-21-11 | D04290J | | 28 | | | | | TB0160X | C005 | BJ | | 050-099 |
| 535 | 24 | | PK | 4-0 | 33-21-11 | D04290J | | 28 | | | | | TB0160X | C005 | BJ | | 150-199 |
| 535 | 24 | | PK | 8-0 | 33-21-11 | D04290J | | 46 | | | | | S01634 | 1 | C | | 280-299 |
| 538 | 22 | | PA | 5-0 | 52-51-11 | D10320 | | 3 | | | | | TB0174F | C008 | 2 | | ALL |
| 539 | 20 | | PA | 5-0 | 52-51-11 | D10320 | | 2 | | | | | GDX0001 | D.. | 2 | | ALL |
| 540 | 22 | | PA | 2-0 | 52-51-11 | D10320 | | 7 | | | | | D03558 | C1 | | | ALL |
| 541 | 20 | | PA | 5-0 | 52-51-11 | GDX0001 | | | D.. | 2 | | | D03558 | C2 | | | ALL |
| 542 | 22 | | PA | 5-0 | 52-51-11 | D10320 | | 4 | | | | | TB0174F | A008 | 2 | | ALL |
| 566 | 22 | | PA | 5-0 | 33-51-11 | D05088J | | 34 | | | | | TB0146Z | 40 | BJ | | 050-099 |
| 566 | 22 | | PA | 3-0 | 33-51-11 | D05088J | | 34 | | | | | TB0146Z | 40 | BJ | | 150-199, 275-299 |
| 567 | 22 | | PA | 5-0 | 33-51-11 | D05088J | | 35 | | | | | TB0160Z | 11 | BJ | | 050-099 |
| 567 | 22 | | PA | 3-0 | 33-51-11 | D05088J | | 35 | | | | | TB0160Z | 11 | BJ | | 150-199, 275-299 |
| 568 | 22 | | PA | 5-0 | 33-51-11 | D05088J | | 36 | | | | | TB0160Z | 10 | BJ | | 050-099 |
| 568 | 22 | | PA | 3-0 | 33-51-11 | D05088J | | 36 | | | | | TB0160Z | 10 | BJ | | 150-199, 275-299 |
| 569 | 22 | | PA | 3-0 | 33-51-11 | D05076J | | 7 | | | | | TB0160Y | A015 | BJ | | ALL |
| 570 | 22 | | PA | 3-0 | 33-51-11 | D05148J | | 10 | | | | | TB0160Y | C014 | BJ | | ALL |
| 571 | 22 | | PA | 4-0 | 33-51-11 | D05082J | | 14 | | | | | D05170J | 12 | | | ALL |
| 572 | 22 | | PA | 3-0 | 33-51-21 | D05082J | | 24 | | | | | TB0160Z | 11 | BJ | | ALL |
| 573 | 22 | | PA | 3-0 | 33-51-21 | D05076J | | 14 | | | | | TB0160Z | 11 | BJ | | ALL |
| 581 | 20 | | PA | 4-0 | 33-26-21 | D05138J | | 1 | | | | | TB0146Y | A028 | BJ | | 050-099 |
| 581 | 20 | | PA | 3-0 | 33-26-21 | D05138J | | 1 | | | | | TB0146Y | A028 | BJ | | 150-199, 275-299 |
| 582 | 22 | | PA | 4-0 | 25-65-11 | D05088J | | 26 | | | | | D05082J | 18 | | | ALL |
| 583 | 22 | | PA | 4-0 | 25-65-12 | D05088J | | 29 | | | | | D05082J | 15 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 584 | 22 | | PA | 6-0 | 25-65-12 | D10734 | | 2 | | | | | D05082J | 9 | | | ALL |
| 585 | 22 | | PA | 6-0 | 25-65-11 | D10734 | | 10 | | | | | D05082J | 17 | | | ALL |
| 586 | 22 | | PA | 6-0 | 25-65-12 | D10736 | | 2 | | | | | D05082J | 8 | | | ALL |
| 587 | 22 | | PA | 6-0 | 25-65-11 | D10736 | | 10 | | | | | D05082J | 16 | | | ALL |
| 588 | 20 | | PA | 3-0 | 27-61-18 | D05082J | | 19 | | | | | TB0160F | C023 | 2 | | ALL |
| 589 | 20 | | PA | 4-0 | 27-61-18 | D05082J | | 20 | | | | | TB0160F | C038 | 2 | | ALL |
| 591 | 20 | | PA | 4-0 | 33-24-11 | TB0174Y | A013 | | BJ | | | | D04290J | 23 | | | 275-299 |
| 592 | 20 | | PA | 4-0 | 33-24-11 | TB0146Z | | 19 | BJ | | | | D04290J | 26 | | | 275-299 |
| 596 | 22 | | PA | 6-0 | 25-65-11 | D10734 | | 7 | | | | | TB0160H | 3 | 2 | | 050-099 |
| 596 | 22 | | PA | 5-0 | 25-65-11 | D10734 | | 7 | | | | | TB0160H | 3 | 2 | | 150-199, 275-299 |
| 597 | 20 | | PA | 6-0 | 25-65-11 | D10734 | | 11 | | | | | GDX0002 | D.. | 2 | | 050-099 |
| 597 | 20 | | PA | 5-0 | 25-65-11 | D10734 | | 11 | | | | | GDX0002 | D.. | 2 | | 150-199, 275-299 |
| 598 | 22 | | PA | 2-0 | 25-65-11 | D10734 | | 14 | | | | | D10736 | 7 | | | 050-099 |
| 598 | 22 | | PA | 1-0 | 25-65-11 | D10734 | | 14 | | | | | D10736 | 7 | | | 150-199, 275-299 |
| 599 | 20 | | PA | 6-0 | 25-65-11 | D10736 | | 11 | | | | | GDX0002 | D.. | 2 | | 050-099 |
| 599 | 20 | | PA | 5-0 | 25-65-11 | D10736 | | 11 | | | | | GDX0002 | D.. | 2 | | 150-199, 275-299 |
| 600 | 20 | | PA | 3-0 | 33-22-11 | D04290J | | 13 | | | | | TB0174Z | 37 | BJ | | 050-099 |
| 600 | 20 | | PA | 4-0 | 33-22-11 | D04290J | | 13 | | | | | TB0174Z | 37 | BJ | | 150-199 |
| 600 | 20 | | PA | 4-0 | 33-24-11 | D03560 | | | C1 | | | | TB0174Z | 37 | BJ | | 275-299 |
| 601 | 22 | | PA | 6-0 | 25-65-12 | D10736 | | 6 | | | | | TB0160H | 1 | 2 | | 050-099 |
| 601 | 22 | | PA | 5-0 | 25-65-12 | D10736 | | 6 | | | | | TB0160H | 1 | 2 | | 150-199, 275-299 |
| 602 | 22 | | PA | 6-0 | 25-65-12 | D10734 | | 5 | | | | | TB0160H | 1 | 2 | | 050-099 |
| 602 | 22 | | PA | 5-0 | 25-65-12 | D10734 | | 5 | | | | | TB0160H | 1 | 2 | | 150-199, 275-299 |
| 603 | 20 | | PA | 6-0 | 25-65-12 | D10734 | | 1 | | | | | GDX0002 | D.. | 2 | | 050-099 |
| 603 | 20 | | PA | 5-0 | 25-65-12 | D10734 | | 1 | | | | | GDX0002 | D.. | 2 | | 150-199, 275-299 |
| 604 | 22 | | PA | 6-0 | 25-65-12 | D10734 | | 6 | | | | | TB0160H | 1 | 2 | | 050-099 |
| 604 | 22 | | PA | 5-0 | 25-65-12 | D10734 | | 6 | | | | | TB0160H | 1 | 2 | | 150-199, 275-299 |
| 605 | 22 | | PA | 2-0 | 25-65-12 | D10734 | | 3 | | | | | D10736 | 5 | | | 050-099 |
| 605 | 22 | | PA | 1-0 | 25-65-12 | D10734 | | 3 | | | | | D10736 | 5 | | | 150-199, 275-299 |
| 606 | 22 | | PA | 4-0 | 25-65-12 | D10734 | | 12 | | | | | D05088J | 37 | | | ALL |
| 607 | 20 | | PA | 6-0 | 25-65-12 | D10736 | | 1 | | | | | GDX0002 | D.. | 2 | | 050-099 |
| 607 | 20 | | PA | 5-0 | 25-65-12 | D10736 | | 1 | | | | | GDX0002 | D.. | 2 | | 150-199, 275-299 |
| 608 | 22 | | PA | 4-0 | 25-65-12 | D10736 | | 12 | | | | | D05088J | 39 | | | ALL |
| 617 | 20 | | PA | 4-0 | 33-26-21 | D04290J | | 44 | | | | | D10898 | A2 | | | 050-099, 275-278 |
| 617 | 20 | | PA | 4-0 | 33-26-21 | D10898 | | A2 | | | | | D04290J | 44 | | | 150-199 |
| 617 | 22 | | PA | 4-0 | 33-26-21 | D04290J | | 44 | | | | | D10898 | A2 | | | 280-299 |
| 618 | 20 | | PA | 5-0 | 33-26-21 | GDX0002 | | D.. | 2 | | | | D10898 | A1 | | | 050-099 |
| 618 | 20 | | PA | 5-0 | 33-26-21 | D10898 | | A1 | | | | | GDX0002 | D.. | 2 | | 150-199, 275-299 |
| 619 | 20 | | PA | 5-0 | 33-26-21 | GDX0002 | | A.. | 2 | | | | D10898 | X2 | | | 050-099 |

WIRE LIST

D280T132

91-21-11
Section W1060
Page 12
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 619 | 20 | | PA | 5-0 | 33-26-21 | D10898 | | X2 | | | | | GDX0002 | A.. | 2 | | 150-199, 275-299 |
| 620 | 20 | | PA | 5-0 | 33-26-21 | TB0146Y | | C005 | BJ | | | | D10898 | X1 | | | 050-099 |
| 620 | 20 | | PA | 5-0 | 33-26-21 | D10898 | | X1 | | | | | TB0146X | A007 | BJ | | 150-157 |
| 620 | 20 | | PA | 4-0 | 33-26-21 | TB0160Y | | C017 | BJ | | | | D10898 | X1 | | | 162-199 |
| 620 | 22 | | PA | 4-0 | 33-26-21 | D10898 | | X1 | | | | | TB0146X | A007 | BJ | | 275-278 |
| 620 | 22 | | PA | 4-0 | 33-26-21 | D10898 | | X1 | | | | | TB0160Y | C017 | BJ | | 280-299 |
| 621 | 22 | | PA | 2-0 | 33-21-21 | TB0146Z | | 34 | BJ | | | | TB0146Z | 33 | BJ | | 162-199 |
| 621 | 22 | | PA | 7-0 | 33-21-21 | S00435 | | 3 | C | | * | | D03556 | B1 | | | 275-299 |
| 622 | 22 | | PA | 6-0 | 33-21-21 | D10794 | | A1 | | | | | S00435 | 3 | C | * | 275-299 |
| 624 | 22 | | PA | 2-0 | 33-21-21 | TB0146Z | | 34 | BJ | | | | TB0146Z | 33 | BJ | | 050-099 |
| 624 | 22 | | PA | 3-0 | 33-21-21 | TB0146Y | | C012 | BJ | | | | TB0146Z | 33 | BJ | | 150-157 |
| 624 | 22 | | PA | 3-0 | 33-21-21 | D10794 | | X1 | | | | | TB0146Z | 33 | BJ | | 275-278 |
| 624 | 22 | | PA | 4-0 | 33-21-21 | D10794 | | X1 | | | | | TB0146Y | C012 | BJ | | 280-299 |
| 625 | 22 | | PA | 4-0 | 33-21-21 | D10794 | | X2 | | | | | TB0174X | A019 | BJ | | ALL |
| 628 | 22 | | PA | 3-0 | 33-22-41 | D10794 | | B2 | | | | | D05170J | 14 | | | 275-278 |
| 628 | 22 | | PA | 4-0 | 33-22-41 | D10794 | | B2 | | | | | D05170J | 14 | | | 280-299 |
| 629 | 22 | | PA | 4-0 | 33-22-41 | TB0146Y | | A002 | BJ | | | | D04290J | 9 | | | 050-099 |
| 629 | 22 | | PA | 3-0 | 33-22-41 | TB0146Y | | A002 | BJ | | | | D04290J | 9 | | | 150-199 |
| 629 | 22 | | PA | 4-0 | 33-22-41 | D10794 | | B1 | | | | | D04290J | 40 | | | 275-299 |
| 630 | 22 | | PA | 4-0 | 33-22-41 | TB0146Z | | 34 | BJ | | | | D03558 | A2 | | | 050-099 |
| 630 | 22 | | PA | 2-0 | 33-22-41 | TB0146Z | | 33 | BJ | | | | TB0146Y | A038 | BJ | | 150-199 |
| 630 | 22 | | PA | 4-0 | 33-22-41 | TB0146Z | | 33 | BJ | | | | D03558 | A2 | | | 275-299 |
| 631 | 22 | | PA | 4-0 | 33-22-41 | D10794 | | C1 | | | | | TB0160Y | C015 | BJ | | 050-099 |
| 631 | 22 | | PA | 3-0 | 33-22-41 | D10794 | | C1 | | | | | TB0160Y | C015 | BJ | | 150-199, 275-299 |
| 632 | 22 | | PA | 5-0 | 33-22-41 | D04290J | | 7 | | | | | TB0160Y | C015 | BJ | | ALL |
| 633 | 22 | | PA | 3-0 | 33-22-42 | D05148J | | 25 | | | | | TB0174X | B019 | BJ | | ALL |
| 640 | 20 | | PA | 3-0 | 33-51-11 | TB0160H | | 3 | 2 | | | | TB0160G | 37 | 2 | | ALL |
| 641 | 22 | | PA | 4-0 | 33-51-11 | TB0160Z | | 10 | BJ | | | | D06410J | 8 | | | ALL |
| 642 | 20 | | PA | 3-0 | 33-51-11 | TB0160H | | 1 | 2 | | | | TB0146Z | 40 | BJ | | ALL |
| 669 | 24 | | PK | 8-0 | 33-21-11 | D04290J | | 45 | | | | | S01634 | 4 | C | | 280-299 |
| 679 | 22 | | PA | 4-0 | 33-21-21 | D10794 | | D1 | | | | | TB0174Y | A013 | BJ | | 050-099, 150-199 |
| 679 | 22 | | PA | 8-0 | 33-21-21 | D10794 | | D1 | | | | | S00845 | 1 | C | * | 280-299 |
| 680 | 22 | | PA | 3-0 | 33-21-21 | D10794 | | D2 | | | | | TB0146Z | 34 | BJ | | 050-099 |
| 680 | 22 | | PA | 3-0 | 33-21-21 | TB0146Y | | C012 | BJ | | | | D10794 | D2 | | | 150-157 |
| 680 | 22 | | PA | 5-0 | 33-21-21 | D10794 | | D2 | | | | | TB0146Y | C012 | BJ | | 280-299 |
| 682 | 22 | | PA | 4-0 | 33-21-21 | D11922 | | B2 | | | | | TB0146Z | 34 | BJ | | 050-099 |
| 682 | 22 | | PA | 4-0 | 33-21-21 | TB0146Y | | C012 | BJ | | | | D11922 | B2 | | | 150-157 |
| 682 | 22 | | PA | 5-0 | 33-21-21 | D11922 | | A2 | | | | | TB0146Y | C012 | BJ | | 280-299 |
| 686 | 22 | | PA | 4-0 | 33-21-21 | D03556 | | B2 | | | | | TB0146Z | 34 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 686 | 22 | | PA | | 5-0 | 33-21-21 | TB0146Y | C012 | BJ | | D03556 | B2 | | | 150-157 |
| 687 | 20 | | PA | | 2-0 | 33-21-31 | TB0146Y | A032 | BJ | | TB0174Z | 28 | BJ | | 155-157, 166-199 |
| 690 | 22 | | PA | | 3-0 | 33-22-41 | D04290J | 49 | | | TB0160Y | C016 | BJ | | 050-099 |
| 690 | 22 | | PA | | 5-0 | 33-22-41 | D05170J | 32 | | | TB0160Y | C016 | BJ | | 150-199 |
| 692 | 22 | | PA | | 2-0 | 30-46-11 | TB0174Z | 27 | BJ | | D05088J | 45 | | | ALL |
| 693 | 22 | | PA | | 2-0 | 30-46-11 | TB0174Z | 27 | BJ | | D05088J | 53 | | | ALL |
| 694 | 22 | | PA | | 2-0 | 30-46-11 | TB0174Z | 27 | BJ | | D05170J | 13 | | | ALL |
| 695 | 22 | | PA | | 3-0 | 30-46-11 | TB0174Z | 27 | BJ | | D05082J | 27 | | | ALL |
| 699 | 20 | | PA | | 3-0 | 33-22-31 | D05170J | 8 | | | TB0174Z | 37 | BJ | | 050-099 |
| 699 | 20 | | PA | | 5-0 | 33-22-31 | D05170J | 8 | | | TB0174Z | 37 | BJ | | 150-199 |
| 700 | 22 | | PA | | 4-0 | 33-22-41 | D10794 | B2 | | | TB0146Y | A018 | BJ | | 050-099 |
| 701 | 22 | | PA | | 4-0 | 33-21-21 | S01639 | 2 | C | * | D05138J | 3 | | | 275-299 |
| 706 | 22 | | PA | | 7-0 | 33-21-21 | D11922 | X1 | | | D13360 | C2 | | | 050-099 |
| 706 | 22 | | PA | | 7-0 | 33-21-21 | D13360 | C2 | | | D11922 | X1 | | | 150-199 |
| 706 | 24 | | PK | | 5-0 | 33-21-21 | D04290J | 50 | | | D11922 | X1 | | | 280-299 |
| 707 | 20 | | PA | | 5-0 | 33-21-21 | D11922 | X2 | | | GDX0002 | A.. | 2 | | 050-099, 280-299 |
| 707 | 22 | | PA | | 5-0 | 33-21-21 | D11922 | X2 | | | GDX0002 | A.. | 2 | | 150-199 |
| 708 | 22 | | PA | | 5-0 | 33-21-21 | D11922 | B1 | | | TB0174Y | A013 | BJ | | 050-099, 150-199 |
| 708 | 22 | | PA | | 8-0 | 33-21-21 | D11922 | A1 | | | S00845 | 1 | C | * | 280-299 |
| 709 | 24 | | PK | | 4-0 | 33-21-31 | D04290J | 60 | | | TB0174X | D001 | BJ | | 050-099, 150-199 |
| 709 | 24 | | PK | | 3-0 | 33-21-31 | D04290J | 42 | | | TB0174X | D001 | BJ | | 280-299 |
| 710 | 20 | | PA | | 3-0 | 33-22-32 | D04290J | 52 | | | TB0174Z | 37 | BJ | | 050-099 |
| 710 | 20 | | PA | | 4-0 | 33-22-32 | TB0174Z | 37 | BJ | | D04290J | 52 | | | 150-199 |
| 710 | 20 | | PA | | 4-0 | 33-24-11 | D05148J | 41 | | | TB0174Y | A013 | BJ | | 275-278 |
| 710 | 20 | | PA | | 2-0 | 33-24-11 | TB0146Y | A014 | BJ | | TB0174Y | A013 | BJ | | 280-299 |
| 711 | 20 | | PA | | 3-0 | 33-22-11 | D05170J | 4 | | | TB0174Z | 37 | BJ | | 050-099 |
| 711 | 20 | | PA | | 4-0 | 33-22-11 | D05170J | 4 | | | TB0174Z | 37 | BJ | | 150-199 |
| 711 | 20 | | PA | | 3-0 | 33-24-11 | TB0174Z | 38 | BJ | | D05170J | 36 | | | 275-299 |
| 712 | 22 | | PA | | 3-0 | 33-24-11 | D05170J | 35 | | | TB0146Z | 20 | BJ | | 050-099 |
| 712 | 20 | | PA | | 3-0 | 33-24-11 | TB0146Z | 20 | BJ | | D05170J | 35 | | | 275-299 |
| 713 | 22 | | PA | | 5-0 | 33-24-11 | D05162J | 7 | | | TB0174Z | 38 | BJ | | 050-099 |
| 714 | 22 | | PA | | 4-0 | 33-24-11 | D02254 | D1 | | | TB0174Z | 38 | BJ | | 050-099 |
| 714 | 20 | | PA | | 4-0 | 33-24-11 | D02254 | D1 | | | TB0174Z | 38 | BJ | | 275-299 |
| 715 | 20 | | PA | | 4-0 | 33-24-11 | D05148J | 40 | | | TB0146Z | 19 | BJ | | 275-278 |
| 715 | 20 | | PA | | 2-0 | 33-24-11 | TB0146Y | C014 | BJ | | TB0146Z | 19 | BJ | | 280-299 |
| 717 | 20 | | PA | | 4-0 | 33-26-11 | D05088J | 51 | | | TB0146Y | C001 | BJ | | 050-099 |
| 717 | 20 | | PA | | 6-0 | 33-26-11 | D05088J | 51 | | | TB0146Y | C001 | BJ | | 150-199 |
| 720 | 24 | | PK | | 4-0 | 33-21-11 | D04290J | 29 | | | TB0160X | B005 | BJ | | 050-099 |
| 720 | 24 | | PK | | 5-0 | 33-21-11 | D04290J | 29 | | | TB0160X | B005 | BJ | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | |
| 731 | 24 | | PK | 6-0 | 33-21-31 | D13362 | | X1 | | | | TB0174Z | 28 | BJ | | 050-099 |
| 731 | 24 | | PK | 5-0 | 33-21-31 | D13362 | | X1 | | | | TB0174Z | 28 | BJ | | 150-199 |
| 732 | 24 | | PK | 5-0 | 33-21-31 | D13360 | | Y2 | | | | TB0174Y | A014 | BJ | | 155-157, 166-199 |
| 733 | 24 | | PK | 4-0 | 33-21-11 | D04290J | | 51 | | | | TB0160X | D005 | BJ | | 050-099 |
| 733 | 24 | | PK | 5-0 | 33-21-11 | D04290J | | 51 | | | | TB0160X | D005 | BJ | | 150-199 |
| 737 | 24 | | PK | 5-0 | 33-21-11 | D05088J | | 1 | | | | TB0174Z | 28 | BJ | | 150-199 |
| 739 | 24 | | PK | 6-0 | 33-21-31 | D13360 | | A2 | | | | TB0174X | B020 | BJ | | 050-099 |
| 739 | 20 | | PA | 5-0 | 33-21-31 | D13360 | | A2 | | | | TB0174X | B020 | BJ | | 150-199 |
| 740 | 24 | | PK | 5-0 | 33-21-31 | D13362 | | A2 | | | | TB0174Y | C005 | BJ | | 050-099 |
| 740 | 20 | | PA | 5-0 | 33-21-31 | D13362 | | A2 | | | | TB0174X | C020 | BJ | | 150, 153-154 |
| 740 | 20 | | PA | 5-0 | 33-21-31 | D13362 | | A2 | | | | TB0146Y | C043 | BJ | | 151-152, 155-157 |
| 741 | 24 | | PK | 3-0 | 33-21-31 | D05148J | | 43 | | | | TB0174X | D020 | BJ | | 050-099 |
| 741 | 20 | | PA | 5-0 | 33-21-31 | D04290J | | 49 | | | | TB0174X | D020 | BJ | | 150-157 |
| 741 | 24 | | PK | 5-0 | 33-21-31 | D05148J | | 43 | | | | TB0174X | D020 | BJ | | 162-199 |
| 742 | 24 | | PK | 4-0 | 33-21-31 | D13358 | | Y1 | | | | TB0146Y | A032 | BJ | | 050-099, 163-165 |
| 742 | 24 | | PK | 5-0 | 33-21-31 | D13358 | | Y1 | | | | TB0146Y | A032 | BJ | | 150-154, 162 |
| 743 | 24 | | PK | 4-0 | 33-21-31 | D13358 | | X1 | | | | TB0146Y | A032 | BJ | | 050-099, 163-165 |
| 743 | 24 | | PK | 5-0 | 33-21-31 | D13358 | | X1 | | | | TB0146Y | A032 | BJ | | 150-154, 162 |
| 744 | 24 | | PK | 6-0 | 33-21-31 | D13362 | | Y1 | | | | TB0146Y | A032 | BJ | | 050-099 |
| 744 | 24 | | PK | 5-0 | 33-21-31 | D13362 | | Y1 | | | | TB0146Y | A032 | BJ | | 150-154, 162 |
| 744 | 24 | | PK | 4-0 | 33-21-31 | D13362 | | Y1 | | | | TB0146Y | A032 | BJ | | 163-165 |
| 745 | 24 | | PK | 4-0 | 33-21-31 | D13358 | | X2 | | | | TB0146Y | C031 | BJ | | 050-099 |
| 745 | 24 | | PK | 5-0 | 33-21-31 | D13358 | | X2 | | | | TB0146Y | C031 | BJ | | 150-199 |
| 746 | 24 | | PK | 4-0 | 33-21-31 | D13358 | | A1 | | | | D04290J | 58 | | | 050-099 |
| 746 | 20 | | PA | 5-0 | 33-21-31 | D04290J | | 58 | | | | D13358 | A1 | | | 150-157 |
| 746 | 24 | | PK | 5-0 | 33-21-31 | D04290J | | 58 | | | | D13358 | A1 | | | 162-199 |
| 747 | 24 | | PK | 4-0 | 33-21-31 | D13358 | | A3 | | | | D04290J | 19 | | | 050-099 |
| 747 | 20 | | PA | 5-0 | 33-21-31 | D04290J | | 19 | | | | D13358 | A3 | | | 150-157 |
| 747 | 24 | | PK | 5-0 | 33-21-31 | D04290J | | 19 | | | | D13358 | A3 | | | 162-199 |
| 748 | 24 | | PK | 6-0 | 33-21-31 | D04290J | | 47 | | | | D13360 | A3 | | | 050-099, 162-199 |
| 748 | 20 | | PA | 6-0 | 33-21-31 | D04290J | | 47 | | | | D13360 | A3 | | | 150-157 |
| 749 | 24 | | PK | 6-0 | 33-21-31 | D04290J | | 59 | | | | D13360 | A1 | | | 050-099, 162-199 |
| 749 | 20 | | PA | 6-0 | 33-21-31 | D04290J | | 59 | | | | D13360 | A1 | | | 150-157 |
| 750 | 24 | | PK | 5-0 | 33-21-31 | D05138J | | 8 | | | | D13362 | A3 | | | 050-099 |
| 750 | 20 | | PA | 5-0 | 33-21-31 | D13362 | | A3 | | | | D05138J | 8 | | | 150-157 |
| 750 | 24 | | PK | 5-0 | 33-21-31 | D13362 | | A3 | | | | D05138J | 8 | | | 162-199 |
| 751 | 24 | | PK | 5-0 | 33-21-31 | D13362 | | X2 | | | | TB0174Y | A005 | BJ | | 050-099, 150-199 |
| 752 | 22 | | PA | 5-0 | 33-22-41 | D03558 | | A2 | | | | TB0146Y | A038 | BJ | | 150-199 |
| 754 | 22 | | PA | 6-0 | 33-21-21 | D13360 | | C3 | | | | D04290J | 46 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 754 | 22 | | PA | | 7-0 | 33-21-21 | D13360 | | | | C3 | | | | 150-199 |
| 756 | 22 | | PA | | 6-0 | 33-21-21 | D13360 | | | | C1 | | | | 050-099, 150-199 |
| 757 | 22 | | PA | | 4-0 | 33-21-21 | D13358 | | | | C1 | | | | 050-099 |
| 757 | 22 | | PA | | 6-0 | 33-21-21 | D13358 | | | | C1 | | | | 150-199 |
| 758 | 22 | | PA | | 3-0 | 33-21-21 | D13358 | | | | C2 | | | | 050-099, 150-199 |
| 759 | 24 | | PK | | 6-0 | 33-21-31 | D04290J | | | | 61 | | | | 050-099, 162-199 |
| 759 | 20 | | PA | | 6-0 | 33-21-31 | D04290J | | | | 61 | | | | 150-157 |
| 760 | 24 | | PK | | 5-0 | 33-21-31 | D05138J | | | | 4 | | | | 050-099 |
| 760 | 24 | | PK | | 6-0 | 33-21-31 | D13362 | | | | Y2 | | | | 150-199 |
| 761 | 24 | | PK | | 5-0 | 33-21-31 | D13360 | | | | Y2 | | | | 050-099 |
| 761 | 24 | | PK | | 5-0 | 33-21-31 | TB0174Y | A014 | | | BJ | | | | 150-154, 162 |
| 761 | 24 | | PK | | 4-0 | 33-21-31 | TB0174Y | A014 | | | BJ | | | | 163-165 |
| 762 | 24 | | PK | | 4-0 | 33-21-11 | D04290J | | | | 43 | | | | 050-099, 150-199 |
| 763 | 22 | | PA | | 4-0 | 33-22-41 | D13358 | | | | D3 | | | | 050-099 |
| 763 | 22 | | PA | | 6-0 | 33-22-41 | D13358 | | | | D3 | | | | 150-199 |
| 764 | 22 | | PA | | 4-0 | 33-22-41 | D13358 | | | | B3 | | | | 050-099 |
| 764 | 22 | | PA | | 6-0 | 33-22-41 | D13358 | | | | B3 | | | | 150-199 |
| 765 | 22 | | PA | | 4-0 | 33-22-41 | D13358 | | | | B2 | | | | 050-099 |
| 765 | 22 | | PA | | 6-0 | 33-22-41 | D13358 | | | | B2 | | | | 150-199 |
| 766 | 22 | | PA | | 4-0 | 33-22-41 | D13358 | | | | D2 | | | | 050-099 |
| 766 | 22 | | PA | | 6-0 | 33-22-41 | D13358 | | | | D2 | | | | 150-199 |
| 767 | 22 | | PA | | 4-0 | 33-22-41 | D13358 | | | | D1 | | | | 050-099 |
| 767 | 22 | | PA | | 5-0 | 33-22-41 | D13358 | | | | D1 | | | | 150-199 |
| 768 | 22 | | PA | | 4-0 | 33-22-41 | D13358 | | | | B1 | | | | 050-099 |
| 768 | 22 | | PA | | 5-0 | 33-22-41 | D13358 | | | | B1 | | | | 150-199 |
| 770 | 22 | | PA | | 3-0 | 33-22-41 | D04290J | | | | 48 | | | | 050-099 |
| 770 | 22 | | PA | | 5-0 | 33-22-41 | D04290J | | | | 48 | | | | 150-199 |
| 772 | 22 | | PA | | 6-0 | 33-22-41 | D03558 | | | | X1 | | | | 150-199 |
| 773 | 24 | | PK | | 6-0 | 33-21-31 | D13360 | | | | Y1 | | | | 050-099 |
| 773 | 24 | | PK | | 5-0 | 33-21-31 | TB0174Z | | | | 28 | | | | 150-199 |
| 774 | 22 | | PA | | 4-0 | 33-22-41 | D04290J | | | | 40 | | | | 050-099 |
| 774 | 22 | | PA | | 6-0 | 33-22-41 | D04290J | | | | 40 | | | | 150-199 |
| 777 | 24 | | PK | | 3-0 | 33-21-12 | D05082J | | | | 30 | | | | 050-099 |
| 777 | 24 | | PK | | 4-0 | 33-21-12 | D05082J | | | | 30 | | | | 150-199 |
| 778 | 24 | | PK | | 4-0 | 33-21-12 | D05082J | | | | 31 | | | | 050-099 |
| 778 | 24 | | PK | | 5-0 | 33-21-12 | D05082J | | | | 31 | | | | 150-199 |
| 779 | 22 | | PA | | 2-0 | 33-21-21 | S01639 | | | | 3 | | | | 275-299 |
| 780 | 22 | | PA | | 5-0 | 33-21-21 | S01639 | | | | 1 | | | | 275-299 |
| 781 | 22 | | PA | | 4-0 | 33-21-21 | D10794 | | | | A1 | | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1060 | 286T1060 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 781 | 22 | | PA | 5-0 | 33-21-21 | D10794 | | A1 | | | | | TB0146Y | A012 | BJ | | 150-199 |
| 782 | 22 | | PA | 5-0 | 33-24-11 | D05162J | | 4 | | | | | TB0174Z | 36 | BJ | | 050-099 |
| 783 | 20 | | PA | 3-0 | 33-24-11 | D05170J | | 9 | | | | | TB0146Z | 19 | BJ | | 050-099 |
| 783 | 20 | | PA | 4-0 | 33-24-11 | D05170J | | 9 | | | | | TB0146Z | 14 | BJ | | 150-199 |
| 784 | 20 | | PA | 3-0 | 33-24-11 | D05170J | | 10 | | | | | TB0146Z | 20 | BJ | | 050-099 |
| 784 | 20 | | PA | 4-0 | 33-24-11 | D05170J | | 10 | | | | | TB0146Z | 13 | BJ | | 150-199 |
| 787 | 20 | | PA | 3-0 | 33-24-11 | D05170J | | 33 | | | | | TB0174Z | 38 | BJ | | 050-099 |
| 787 | 20 | | PA | 4-0 | 33-24-11 | D05170J | | 33 | | | | | TB0146Z | 14 | BJ | | 150-199 |
| 788 | 20 | | PA | 3-0 | 33-24-11 | D05170J | | 34 | | | | | TB0174Z | 36 | BJ | | 050-099 |
| 788 | 20 | | PA | 4-0 | 33-24-11 | D05170J | | 34 | | | | | TB0146Z | 13 | BJ | | 150-199 |
| 790 | 24 | | PK | 5-0 | 33-21-31 | D13358 | | Y2 | | | | | TB0146Y | C002 | BJ | | 050-099, 150-199 |
| 792 | 20 | | PA | 5-0 | 33-24-11 | D05170J | | 38 | | | | | TB0146Y | C014 | BJ | | 280-299 |
| 793 | 20 | | PA | 5-0 | 33-24-11 | D05170J | | 37 | | | | | TB0146Y | A014 | BJ | | 280-299 |
| 800 | 20 | | PA | 3-0 | 26-13-12 | D05170J | | 44 | | | | | TB0146X | C041 | BJ | | 162-199 |
| 804 | 24 | | PK | 6-0 | 33-21-31 | D13360 | | X1 | | | | | TB0174Z | 28 | BJ | | 050-099 |
| 804 | 20 | | PA | 5-0 | 33-21-31 | D13360 | | X1 | | | | | TB0174Z | 28 | BJ | | 150-154 |
| 804 | 24 | | PK | 5-0 | 33-21-31 | D13360 | | X1 | | | | | TB0174Z | 28 | BJ | | 155-199 |
| 806 | 24 | | PK | 6-0 | 33-21-12 | D04290J | | 23 | | | | | TB0174Y | C025 | BJ | | 050-099 |
| 806 | 24 | | PK | 3-0 | 33-21-12 | D04290J | | 23 | | | | | TB0174Y | C025 | BJ | | 150-199 |
| 807 | 24 | | PK | 4-0 | 33-21-12 | D04290J | | 55 | | | | | TB0174Y | C011 | BJ | | 050-099 |
| 807 | 24 | | PK | 3-0 | 33-21-12 | D04290J | | 55 | | | | | TB0174Y | C011 | BJ | | 150-199 |
| 809 | 24 | | PK | 4-0 | 33-21-12 | D04290J | | 6 | | | | | TB0174Y | A011 | BJ | | 050-099 |
| 809 | 24 | | PK | 3-0 | 33-21-12 | D04290J | | 6 | | | | | TB0174Y | A011 | BJ | | 150-199 |
| 811 | 22 | | PA | 5-0 | 33-22-42 | D05148J | | 46 | | | | | D04290J | 55 | | | 275-299 |
| 812 | 20 | | PA | 2-0 | 33-24-11 | TB0174Y | | A013 | BJ | | | | TB0146Z | 20 | BJ | | 275-299 |
| 816 | 20 | | PA | 5-0 | 33-51-13 | D05076J | | 10 | | | | | D05170J | 52 | | | 050-099 |
| 816 | 20 | | PA | 4-0 | 33-51-13 | D05076J | | 10 | | | | | D05170J | 52 | | | 162-199 |
| 820 | 20 | | PA | 5-0 | 35-21-14 | D05170J | | 55 | | | | | TB0160H | 35 | 2 | | 050-099 |
| 820 | 20 | | PA | 4-0 | 35-21-14 | D05170J | | 55 | | | | | TB0160H | 35 | 2 | | 162-199 |
| 821 | 22 | | PA | 4-0 | 33-21-21 | D05148J | | 22 | | | | | TB0146Z | 34 | BJ | | 050-099 |
| 821 | 22 | | PA | 4-0 | 33-21-21 | TB0146Z | | 34 | BJ | | | | D05148J | 22 | | | 162-199 |
| 822 | 22 | | PA | 3-0 | 33-22-33 | D05088J | | 55 | | | | | D05170J | 54 | | | 050-099, 162-199 |
| 823 | 20 | | PA | 4-0 | 33-26-21 | D05170J | | 46 | | | | | TB0146Y | C005 | BJ | | 050-099 |
| 823 | 20 | | PA | 3-0 | 33-26-21 | TB0160Y | | C017 | BJ | | | | D05170J | 46 | | | 162-199 |
| 824 | 20 | | PA | 3-0 | 26-13-12 | D05170J | | 43 | | | | | TB0174Z | 43 | BJ | | 050-099 |
| 825 | 20 | | PA | 3-0 | 26-13-12 | D05170J | | 44 | | | | | TB0174X | A032 | BJ | | 050-099 |
| 826 | 20 | | PA | 3-0 | 26-13-12 | D05170J | | 45 | | | | | TB0174Z | 42 | BJ | | 050-099 |
| 827 | 20 | | PA | 4-0 | 26-13-12 | D05148J | | 24 | | | | | TB0174Z | 43 | BJ | | 050-099 |
| 828 | 20 | | PA | 4-0 | 26-13-12 | D05148J | | 6 | | | | | TB0174Z | 41 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 17

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|------------------------------------|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1060 | 286T1060 | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 829 | 20 | | PA | | 4-0 | 26-13-12 | D05148J | | 15 | | TB0174Z | 42 | BJ | | 050-099 |
| 830 | 20 | | PA | | 4-0 | 26-13-12 | D05148J | | 17 | | TB0174X | A031 | BJ | | 050-099 |
| 831 | 24 | | PK | | 3-0 | 33-21-31 | D05148J | | 44 | | TB0174Y | C012 | BJ | | 050-099 |
| 831 | 24 | | PK | | 5-0 | 33-21-31 | D05148J | | 44 | | TB0174Y | C013 | BJ | | 162-199 |
| 832 | 22 | | PA | | 3-0 | 33-24-11 | D05170J | | 36 | | TB0146Z | 19 | BJ | | 050-099 |
| 842 | 20 | | PA | | 3-0 | 26-13-12 | D05170J | | 47 | | TB0174Y | C026 | BJ | | 050-099 |
| 842 | 20 | | PA | | 3-0 | 26-13-12 | D05170J | | 47 | | TB0174Y | C043 | BJ | | 162-199 |
| 843 | 20 | | PA | | 3-0 | 26-13-12 | D05170J | | 45 | | TB0174Y | A043 | BJ | | 162-199 |
| 844 | 20 | | PA | | 4-0 | 26-13-12 | TB0174Y | A042 | BJ | | D05148J | 24 | | | 162-199 |
| 845 | 20 | | PA | | 4-0 | 26-13-12 | TB0174Y | C042 | BJ | | D05148J | 6 | | | 162-199 |
| 846 | 20 | | PA | | 4-0 | 26-13-12 | TB0174Y | A043 | BJ | | D05148J | 15 | | | 162-199 |
| 847 | 20 | | PA | | 4-0 | 26-13-12 | TB0146X | D041 | BJ | | D05148J | 17 | | | 162-199 |
| 848 | 20 | | PA | | 4-0 | 26-13-12 | D05148J | | 55 | | TB0174Y | C026 | BJ | | 050-099 |
| 848 | 20 | | PA | | 4-0 | 26-13-12 | TB0174Y | C043 | BJ | | D05148J | 55 | | | 162-199 |
| 849 | 22 | | PA | | 3-0 | 33-22-21 | D06412J | | 7 | | TB0146Y | A043 | BJ | | 162-199 |
| 850 | 22 | | PA | | 4-0 | 33-22-21 | D05076J | | 36 | | TB0146Y | A043 | BJ | | 162-199 |
| 851 | 24 | | PK | | 5-0 | 33-21-31 | D13362 | | A2 | | TB0146Y | C043 | BJ | | 162-199 |
| 852 | 22 | | PA | | 4-0 | 21-66-21 | D05148J | | 26 | | D05088J | 12 | | | 050-099 |
| 852 | 22 | | PA | | 5-0 | 21-66-21 | D05088J | | 12 | | D05148J | 26 | | | 162-199 |
| 853 | 22 | | PA | | 4-0 | 21-66-21 | D05148J | | 27 | | D05088J | 17 | | | 050-099 |
| 853 | 22 | | PA | | 5-0 | 21-66-21 | D05088J | | 17 | | D05148J | 27 | | | 162-199 |
| 854 | 22 | | PA | | 4-0 | 21-66-21 | D05148J | | 34 | | D05088J | 22 | | | 050-099 |
| 854 | 22 | | PA | | 5-0 | 21-66-21 | D05088J | | 22 | | D05148J | 34 | | | 162-199 |
| 855 | 22 | | PA | | 4-0 | 21-66-21 | D05148J | | 35 | | D05088J | 33 | | | 050-099 |
| 855 | 22 | | PA | | 5-0 | 21-66-21 | D05088J | | 33 | | D05148J | 35 | | | 162-199 |
| 857 | 22 | | PA | | 4-0 | 21-66-21 | D05148J | | 40 | | D05088J | 43 | | | 050-099 |
| 857 | 22 | | PA | | 5-0 | 21-66-21 | D05088J | | 43 | | D05148J | 40 | | | 162-199 |
| 858 | 22 | | PA | | 3-0 | 21-66-21 | D05088J | | 44 | | TB0146Y | A044 | BJ | | 050-099, 162-199 |
| 859 | 22 | | PA | | 4-0 | 21-66-21 | D05148J | | 36 | | TB0146Y | A044 | BJ | | 050-099 |
| 859 | 22 | | PA | | 4-0 | 21-66-21 | TB0146Y | A044 | BJ | | D05148J | 36 | | | 162-199 |
| 860 | 22 | | PA | | 4-0 | 21-66-21 | D05148J | | 41 | | TB0146Y | A044 | BJ | | 050-099 |
| 860 | 22 | | PA | | 4-0 | 21-66-21 | TB0146Y | A044 | BJ | | D05148J | 41 | | | 162-199 |
| 862 | 22 | | PA | | 4-0 | 21-66-31 | D05148J | | 42 | | TB0146Y | C044 | BJ | | 050-099 |
| 862 | 22 | | PA | | 3-4 | 21-66-31 | TB0146Y | C044 | BJ | | D05148J | 42 | | | 150, 152-157 |
| 862 | 22 | | PA | | 4-0 | 21-66-31 | TB0146Y | C044 | BJ | | D05148J | 42 | | | 162-199 |
| 863 | 22 | | PA | | 4-0 | 21-66-31 | D05148J | | 16 | | TB0146Y | A045 | BJ | | 050-099 |
| 863 | 22 | | PA | | 3-5 | 21-66-31 | TB0146Y | A045 | BJ | | D05148J | 16 | | | 150, 152-157 |
| 863 | 22 | | PA | | 4-0 | 21-66-31 | TB0146Y | A045 | BJ | | D05148J | 16 | | | 162-199 |
| 864 | 22 | | PA | | 4-0 | 21-66-41 | D05148J | | 28 | | D05088J | 52 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 18

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|--------------------------------------|-------|------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1060 | 286T1060 | P19 INTEGRATION (continued) | | | | | | | | | | | | | | |
| 864 | 22 | | PA | 3-8 | 21-66-41 | D05088J | | 52 | | | | D05148J | 28 | | 150, 152-157 | |
| 864 | 22 | | PA | 5-0 | 21-66-41 | D05088J | | 52 | | | | D05148J | 28 | | 162-199 | |
| 866 | 22 | | PA | 4-0 | 21-66-41 | D05148J | | 29 | | | | D05088J | 54 | | 050-099 | |
| 866 | 22 | | PA | 3-8 | 21-66-41 | D05088J | | 54 | | | | D05148J | 29 | | 150, 152-157 | |
| 866 | 22 | | PA | 5-0 | 21-66-41 | D05088J | | 54 | | | | D05148J | 29 | | 162-199 | |
| 867 | 22 | | PA | 2-0 | 21-66-11 | D05170J | | 37 | | | | D05090J | 55 | | 050-099 | |
| 867 | 22 | | PA | 3-0 | 21-66-11 | D05170J | | 37 | | | | D05090J | 55 | | 162-199 | |
| 868 | 22 | | PA | 2-0 | 21-66-11 | D05170J | | 38 | | | | D05090J | 42 | | 050-099 | |
| 868 | 22 | | PA | 3-0 | 21-66-11 | D05170J | | 38 | | | | D05090J | 42 | | 162-199 | |
| 869 | 22 | | PA | 2-0 | 21-66-11 | D05170J | | 39 | | | | D05090J | 43 | | 050-099 | |
| 869 | 22 | | PA | 3-0 | 21-66-11 | D05170J | | 39 | | | | D05090J | 43 | | 162-199 | |
| 870 | 22 | | PA | 2-0 | 21-66-11 | D05170J | | 40 | | | | D05090J | 44 | | 050-099 | |
| 870 | 22 | | PA | 3-0 | 21-66-11 | D05170J | | 40 | | | | D05090J | 44 | | 162-199 | |
| 873 | 22 | | PA | 3-0 | 21-66-11 | D05170J | | 41 | | | | TB0146Y | C045 | BJ | 050-099 | |
| 873 | 22 | | PA | 3-0 | 21-66-11 | TB0146Y | | 41 | | | | D05170J | 41 | | 162-199 | |
| 876 | 22 | | PA | 3-0 | 33-22-21 | D05170J | | 15 | | BJ | | TB0146Y | A043 | BJ | 162-199 | |
| 880 | 20 | | PA | 3-0 | 26-13-12 | D05170J | | 27 | | | | TB0174Z | 41 | BJ | 050-099 | |
| 880 | 20 | | PA | 3-0 | 26-13-12 | D05170J | | 27 | | | | TB0174Y | C042 | BJ | 162-199 | |
| 881 | 22 | | PA | 3-0 | 21-66-11 | D05170J | | 48 | | | | TB0146Y | C045 | BJ | 050-099, 162-199 | |
| 884 | 22 | | PA | 6-0 | 33-22-42 | D04290J | | 53 | | | | D05148J | 53 | | 280-299 | |
| 901 | 22 | | PA | 4-11 | 33-22-21 | D05076J | | 36 | | | | SMZ0001 | | S | 150, 153-157 | |
| 901 | 22 | | PA | 4-11 | 33-22-21 | D05110J | | 28 | | | | TB0146Y | A043 | BJ | 162-199 | |
| 902 | 22 | | PA | 4-11 | 33-22-21 | D05110J | | 28 | | | | SMZ0001 | | S | 150, 153-157 | |
| 903 | 22 | | PA | 4-11 | 33-22-21 | D05114J | | 26 | | | | SMZ0001 | | S | 150, 153-157 | |
| 904 | 18 | | PA | 4-0 | 23-31-11 | D03560 | | A1 | | | | D05090J | 18 | DK | 150, 152-199 | |
| PA1 | | | | 0-0 | 99-99-99 | D03602 | | G2 | | | | D03602 | G3 | | ALL | |
| W1061 | 286T1061 | E1-5 SHELF,R ILS G/S COAX | | | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-31-21 | D00377C | | =C5 | | | | D04051J | =C1 | | ALL | |
| 01CX | | 66 | A | 0-5 | 34-31-21 | D00377C | | 5 | | | | D04051J | =A1 | | ALL | |
| W1063 | 286T1063 | E2-2 SHELF,L ATC TOP ANT COAX | | | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-53-13 | D04093P | | =C1 | | | | D00331A | =C71 | | ALL | |
| 01CX | | | JB | 6-0 | 34-53-13 | D04093P | | =A1 | | | | D00331A | 71 | | ALL | |
| W1064 | 286T1064 | P25 INTEGRATION | | | | | | | | | | | | | | |
| 001 | 24 | | PK | 1-4 | 33-21-12 | D05154J | | 31 | | | | TB0162G | 3 | 2 | ALL | |
| 002 | 24 | | PK | 1-5 | 33-21-12 | D05154J | | 37 | | | | TB0162G | 7 | 2 | 050-099, 150-199 | |

WIRE LIST
D280T132

91-21-11
Section W1060
Page 19
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1064 | 286T1064 | | | P25 INTEGRATION (continued) | | | | | | | | | | | | | | |
| 002 | 24 | | PK | 1-5 | 33-21-12 | D05154J | | 5 | | | | | | TB0162G | 7 | 2 | | 275-299 |
| 003 | 22 | | PA | 2-1 | 33-21-21 | D05150J | | 1 | | | | | | TB0162Y | C014 | BJ | | ALL |
| 004 | 22 | | PA | 2-11 | 33-21-21 | D03608 | | B2 | | | | | | TB0148Z | 18 | BJ | | ALL |
| 005 | 24 | | PK | 3-0 | 33-21-21 | D03608 | | X1 | | | | | | TB0162Y | C014 | BJ | | ALL |
| 006 | 24 | | PK | 3-6 | 33-21-21 | D03608 | | X2 | | | | | | D05154J | 4 | | | 275-299 |
| 007 | 22 | | PA | 2-1 | 33-21-21 | D05150J | | 2 | | | | | | TB0148Z | 13 | BJ | | 150-199, 275-299 |
| 008 | 22 | | PA | 3-9 | 33-21-21 | D03640 | | 5 | | | | | | TB0148Z | 18 | BJ | | 050-099, 150-199 |
| 008 | 22 | | PA | 4-0 | 33-21-21 | D03640 | | 5 | | | | | | TB0148Z | 18 | BJ | | 275-299 |
| 009 | 22 | | PA | 3-0 | 33-21-21 | TB0148Z | | 13 | BJ | | | | | D03608 | B1 | | | ALL |
| 010 | 20 | | PA | 2-3 | 33-21-21 | D03640 | | 1 | | | | | | GDX0001 | A.. | 2 | | 050-099 |
| 010 | 20 | | PA | 2-2 | 33-21-21 | D03640 | | 1 | | | | | | GDX0001 | A.. | 2 | | 150-199 |
| 010 | 20 | | PA | 1-11 | 33-21-21 | D03640 | | 1 | | | | | | GDX0001 | A.. | 2 | | 275-299 |
| 011 | 20 | | PA | 2-3 | 33-21-21 | D03640 | | 6 | | | | | | GDX0001 | S.. | 2 | | 050-099 |
| 011 | 20 | | PA | 2-2 | 33-21-21 | D03640 | | 6 | | | | | | GDX0001 | S.. | 2 | | 150-199 |
| 011 | 20 | | PA | 1-11 | 33-21-21 | D03640 | | 6 | | | | | | GDX0001 | S.. | 2 | | 275-299 |
| 012 | 22 | | PA | 2-4 | 33-21-21 | D05144J | | 2 | | | | | | TB0148Z | 13 | BJ | | 150-199, 275-299 |
| 013 | 22 | | PA | 1-8 | 33-21-21 | D05084J | | 15 | | | | | | TB0148Z | 13 | BJ | | ALL |
| 014 | 24 | | PK | 2-10 | 33-21-31 | D05154J | | 10 | | | | | | D05144J | 5 | | | ALL |
| 015 | 20 | | PA | 2-3 | 33-22-11 | D05150J | | 8 | | | | | | D03642 | 3 | | | 050-099, 275-299 |
| 015 | 20 | | PA | 2-6 | 33-22-11 | D05150J | | 8 | | | | | | D03642 | 3 | | | 150-199 |
| 016 | 18 | | PA | 2-6 | 33-22-11 | D03642 | | 5 | | | | | | TB0162H | 32 | 2 | | 050-099 |
| 016 | 18 | | PA | 2-10 | 33-22-11 | D03642 | | 5 | | | | | | TB0162H | 32 | 2 | | 150-199, 275-299 |
| 017 | 18 | | PA | 2-0 | 33-22-11 | D05154J | | 21 | DK | | | | | TB0162H | 32 | 2 | | ALL |
| 018 | 18 | | PA | 1-6 | 33-22-11 | GDX0001 | | A.. | 2 | | | | | D03642 | 1 | | | 050-099, 150-199 |
| 018 | 18 | | PA | 1-3 | 33-22-11 | GDX0001 | | A.. | 2 | | | | | D03642 | 1 | | | 275-299 |
| 019 | 20 | | PA | 1-6 | 33-22-11 | GDX0001 | | S.. | 2 | | | | | D03642 | 6 | | | 050-099, 150-199 |
| 019 | 20 | | PA | 1-3 | 33-22-11 | GDX0001 | | S.. | 2 | | | | | D03642 | 6 | | | 275-299 |
| 020 | 24 | | PK | 2-7 | 33-22-11 | D05150J | | 9 | | | | | | D05154J | 11 | | | ALL |
| 022 | 24 | | PK | 2-7 | 33-22-11 | D05154J | | 12 | | | | | | D05150J | 11 | | | ALL |
| 023 | 24 | | PK | 2-7 | 33-22-11 | D05154J | | 7 | | | | | | D05150J | 12 | | | ALL |
| 024 | 18 | | PA | 1-8 | 33-22-31 | D05150J | | 4 | DL | | | | | TB0162H | 32 | 2 | | 050-099 |
| 024 | 18 | | PA | 1-8 | 33-22-31 | TB0162H | | 32 | 2 | | | | | D05150J | 4 | DL | | 150-199 |
| 024 | 18 | | PA | 1-8 | 33-22-31 | TB0162H | | 32 | 2 | | | | | D05150J | 23 | DL | | 275-278 |
| 025 | 20 | | PA | 1-7 | 33-51-11 | D06414J | | 2 | | | | | | TB0162Y | A011 | BJ | | ALL |
| 026 | 18 | | PA | 2-6 | 33-27-11 | D00090 | | C2 | | | | | | TB0162H | 32 | 2 | | 150-199 |
| 026 | 18 | | PA | 2-0 | 33-22-31 | D05154J | | 1 | | | | | | TB0162H | 32 | 2 | | 275-299 |
| 027 | 18 | | PA | 2-11 | 33-24-12 | D05104J | | 4 | | | | | | D05184J | 4 | | | 050-099 |
| 028 | 18 | | PA | 2-11 | 33-24-12 | D05104J | | 7 | | | | | | D05184J | 7 | | | 050-099 |
| 029 | 22 | | PA | 2-2 | 33-51-11 | D06414J | | 8 | | | | | | TB0162Z | 35 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 20

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1064 | 286T1064 | | | P25 INTEGRATION (continued) | | | | | | | | | | | | | | |
| 029 | 22 | | PA | 2-3 | 33-51-11 | D06414J | | 8 | | | | | | TB0162Z | 35 | BJ | | 150-199, 275-299 |
| 030 | 22 | | PA | 1-7 | 33-51-11 | D06414J | | 4 | | | | | | TB0162Z | 10 | BJ | | ALL |
| 031 | 20 | | PA | 1-9 | 33-24-14 | D05168J | | 4 | | | | | | TB0162Y | A029 | BJ | | 050-099 |
| 032 | 20 | | PA | 1-9 | 33-24-14 | D05168J | | 7 | | | | | | TB0162Y | C029 | BJ | | 050-099 |
| 033 | 20 | | PA | 2-4 | 33-26-21 | D05144J | | 1 | | | | | | TB0148Z | 14 | BJ | | ALL |
| 044 | 22 | | PA | 1-8 | 33-51-11 | D05086J | | 14 | | | | | | TB0162Z | 10 | BJ | | ALL |
| 045 | 22 | | PA | 1-7 | 33-51-11 | D05084J | | 2 | | | | | | TB0162Z | 10 | BJ | | ALL |
| 047 | 22 | | PA | 1-8 | 33-51-11 | D05086J | | 8 | | | | | | TB0162Z | 10 | BJ | | ALL |
| 052 | 22 | | PA | 2-1 | 33-51-11 | D05154J | | 27 | | | | | | TB0162Z | 35 | BJ | | ALL |
| 055 | 20 | | PA | 2-2 | 33-51-11 | TB0162Y | | | A011 | | BJ | | | D05078J | 1 | | | ALL |
| 056 | 20 | | PA | 1-8 | 33-51-11 | TB0162Y | | | A011 | | BJ | | | D05086J | 7 | | | ALL |
| 057 | 22 | | PA | 2-2 | 33-51-11 | D05078J | | 3 | | | | | | TB0162Z | 10 | BJ | | ALL |
| 058 | 22 | | PA | 2-3 | 33-51-11 | D05086J | | 11 | | | | | | TB0162Z | 35 | BJ | | ALL |
| 059 | 22 | | PA | 2-3 | 33-51-11 | D05086J | | 10 | | | | | | TB0162Z | 35 | BJ | | 050-099 |
| 059 | 22 | | PA | 2-3 | 33-51-11 | TB0162Z | | 35 | | | BJ | | | D05086J | 10 | | | 150-199, 275-299 |
| 060 | 22 | | PA | 1-6 | 33-51-11 | D05078J | | 7 | | | | | | TB0162Z | 35 | BJ | | ALL |
| 061 | 22 | | PA | 3-0 | 33-51-11 | D05084J | | 4 | | | | | | TB0162Z | 35 | BJ | | 050-099 |
| 061 | 22 | | PA | 2-2 | 33-51-11 | D05084J | | 4 | | | | | | TB0162Z | 35 | BJ | | 150-199, 275-299 |
| 062 | 20 | | PA | 2-2 | 33-51-11 | D05078J | | 2 | | | | | | TB0162Y | A012 | BJ | | ALL |
| 067 | 20 | | PA | 1-8 | 33-51-11 | D05086J | | 12 | | | | | | TB0162Y | A012 | BJ | | ALL |
| 068 | 20 | | PA | 1-7 | 33-51-11 | D05084J | | 1 | | | | | | TB0162Y | A012 | BJ | | ALL |
| 073 | 22 | | PA | 2-7 | 33-51-21 | D05078J | | 14 | | | | | | D05084J | 7 | | | ALL |
| 074 | 22 | | PA | 2-7 | 33-51-21 | D05078J | | 15 | | | | | | D05084J | 6 | | | ALL |
| 076 | 22 | | PA | 2-7 | 33-51-21 | D05078J | | 17 | | | | | | D05084J | 8 | | | ALL |
| 077 | 20 | | PA | 2-7 | 33-22-42 | D00082 | | X1 | | | | | | TB0162Y | C013 | BJ | | 050-099, 150-199 |
| 077 | 20 | | PA | 2-0 | 33-22-42 | D05150J | | 7 | | | | | | TB0162Z | 18 | BJ | | 275-299 |
| 078 | 22 | | PA | 2-0 | 33-22-42 | D00082 | | A2 | | | | | | TB0162Z | 37 | BJ | | 275-299 |
| 079 | 22 | | PA | 2-0 | 33-22-42 | D00082 | | X1 | | | | | | TB0162Z | 37 | BJ | | 275-299 |
| 080 | 22 | | PA | 2-7 | 33-22-42 | D00082 | | A1 | | | | | | TB0162Y | C016 | BJ | | 050-099 |
| 080 | 20 | | PA | 2-7 | 33-22-42 | D00082 | | A1 | | | | | | TB0162Y | C016 | BJ | | 150-199 |
| 080 | 22 | | PA | 2-5 | 33-22-42 | D00082 | | A1 | | | | | | TB0162X | C023 | BJ | | 275-299 |
| 082 | 22 | | PA | 1-3 | 33-22-42 | D00082 | | X2 | | | | | | D13394 | A2 | | | 050-099, 150-199 |
| 082 | 22 | | PA | 3-1 | 33-22-42 | D00082 | | X2 | | | | | | D05154J | 3 | | | 275-299 |
| 083 | 22 | | PA | 3-1 | 33-22-42 | D13394 | | Y2 | | | | | | TB0162G | 7 | 2 | | 050-099, 150-199 |
| 085 | 22 | | PA | 2-1 | 33-22-42 | D00084 | | B2 | | | | | | D05150J | 20 | | | 275-278 |
| 086 | 22 | | PA | 3-1 | 33-22-42 | D10796 | | A2 | | | | | | TB0162X | A023 | BJ | | 275-278 |
| 086 | 22 | | PA | 2-9 | 33-22-42 | D10796 | | A2 | | | | | | TB0162X | A023 | BJ | | 280-299 |
| 087 | 22 | | PA | 2-6 | 33-22-42 | D00084 | | B1 | | | | | | TB0162Y | C019 | BJ | | 275-278 |
| 088 | 22 | | PA | 2-10 | 33-22-42 | D10796 | | C2 | | | | | | TB0162Y | A019 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 21

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1064 | 286T1064 | | | P25 INTEGRATION (continued) | | | | | | | | | | | | |
| 088 | 22 | PA | | 2-5 | 33-22-42 | D10796 | | C2 | | | | TB0162Z | 38 | BJ | | 150-199 |
| 088 | 22 | PA | | 1-0 | 33-22-42 | TB0162Z | | 37 | BJ | | | TB0162Z | 38 | BJ | | 275-299 |
| 089 | 22 | PA | | 2-6 | 33-22-42 | D00082 | | A2 | | | | TB0162Y | A019 | BJ | | 050-099 |
| 089 | 22 | PA | | 2-1 | 33-22-42 | D00082 | | A2 | | | | TB0162Z | 38 | BJ | | 150-199 |
| 089 | 22 | PA | | 2-0 | 33-22-42 | D00084 | | X1 | | | | TB0162Z | 38 | BJ | | 275-299 |
| 090 | 22 | PA | | 2-0 | 33-22-42 | D00084 | | A2 | | | | TB0162Z | 38 | BJ | | ALL |
| 091 | 22 | PA | | 2-4 | 33-22-42 | D10796 | | B2 | | | | TB0162Z | 38 | BJ | | 050-099 |
| 091 | 22 | PA | | 2-10 | 33-22-42 | D10796 | | B2 | | | | TB0162Y | A019 | BJ | | 150-199 |
| 091 | 22 | PA | | 3-0 | 33-22-42 | D00084 | | X2 | | | | D05154J | 6 | | | 275-299 |
| 092 | 22 | PA | | 2-4 | 33-22-42 | D00084 | | A1 | | | | TB0162X | B023 | BJ | | 050-099 |
| 092 | 22 | PA | | 2-8 | 33-22-42 | D00084 | | A1 | | | | TB0162Y | C012 | BJ | | 150-199, 275-299 |
| 093 | 22 | PA | | 1-6 | 33-22-42 | D05150J | | 23 | | | | TB0148Z | 17 | BJ | | 150, 152-199 |
| 093 | 22 | PA | | 1-6 | 33-22-42 | D05150J | | 23 | | | | TB0162Z | 38 | BJ | | 151 |
| 093 | 22 | PA | | 2-0 | 33-22-42 | D00086 | | X1 | | | | TB0162Z | 38 | BJ | | 275-299 |
| 094 | 22 | PA | | 3-2 | 33-22-42 | D13558 | | 5 | | | | TB0162Y | A019 | BJ | | 050-099 |
| 094 | 22 | PA | | 2-8 | 33-22-42 | D13558 | | 5 | | | | TB0162Z | 38 | BJ | | 150-199 |
| 094 | 22 | PA | | 2-0 | 33-22-42 | D00086 | | A2 | | | | TB0162Z | 38 | BJ | | 275-299 |
| 095 | 22 | PA | | 3-0 | 33-22-42 | D00086 | | X2 | | | | D05154J | 8 | | | 275-299 |
| 096 | 22 | PA | | 2-0 | 33-22-42 | D00086 | | A1 | | | | TB0162Z | 40 | BJ | | 275-299 |
| 097 | 22 | PA | | 1-9 | 33-21-21 | TB0148Z | | 18 | BJ | | | D05084J | 24 | | | 162-199 |
| 105 | 22 | PA | | 2-3 | 33-27-11 | D05150J | | 3 | | | | TB0162Z | 9 | BJ | | 050-099 |
| 105 | 22 | PA | | 2-6 | 33-27-11 | D05150J | | 3 | | | | TB0162Z | 9 | BJ | | 150-199, 275-299 |
| 106 | 22 | PA | | 2-7 | 33-27-11 | D00090 | | B1 | | | | TB0162X | D026 | BJ | | 050-099, 150-199 |
| 106 | 22 | PA | | 3-0 | 33-27-11 | D00090 | | B1 | | | | TB0162G | 4 | 2 | | 275-299 |
| 107 | 20 | PQ | N | 2-11 | 33-27-11 | D00090 | | A2 | | | | TB0162Y | A016 | BJ | | 050-099 |
| 107 | 20 | PA | | 2-11 | 33-27-11 | D00090 | | A2 | | | | TB0162Y | A016 | BJ | | 150-199, 275-299 |
| 107Z | | | N | 0-0 | 33-27-11 | D00090 | | DED | | | | TB0162Y | DED | | | 050-099 |
| 108 | 20 | PQ | X | 2-7 | 33-27-11 | D00090 | | A1 | | | | TB0162X | C026 | BJ | | 050-099 |
| 108 | 20 | PA | | 2-7 | 33-27-11 | D00090 | | A1 | | | | TB0162X | C026 | BJ | | 150-199, 275-299 |
| 108Z | | | X | 0-0 | 33-27-11 | D00090 | | DED | | | | TB0162X | DED | | | 050-099 |
| 109 | 22 | PA | | 3-0 | 33-27-11 | D00090 | | B2 | | | | TB0162Z | 9 | BJ | | ALL |
| 110 | 22 | PA | | 3-0 | 33-27-11 | D00090 | | X1 | | | | TB0162Z | 9 | BJ | | ALL |
| 111 | 22 | PA | | 3-4 | 33-27-11 | D00090 | | X2 | | | | D05154J | 25 | | | ALL |
| 112 | 20 | PQ | Q | 2-8 | 33-27-11 | D02896 | | B1 | | | | TB0162X | A026 | BJ | | 050-099 |
| 112 | 20 | PA | | 2-8 | 33-27-11 | D02896 | | B1 | | | | TB0162X | A026 | BJ | | 150-199, 275-299 |
| 112Z | | | Q | 0-0 | 33-27-11 | D02896 | | DED | | | | TB0162X | DED | | | 050-099 |
| 113 | 22 | PA | | 3-1 | 33-27-11 | D02896 | | A2 | | | | TB0162Z | 9 | BJ | | 050-099 |
| 113 | 22 | PA | | 3-2 | 33-27-11 | D02896 | | A2 | | | | TB0162Z | 9 | BJ | | 150-199, 275-299 |
| 114 | 22 | PA | | 2-8 | 33-27-11 | D02896 | | A1 | | | | TB0162X | B026 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 22

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1064 | 286T1064 | | | P25 INTEGRATION (continued) | | | | | | | | | | | | | |
| 114 | 22 | | PA | | 2-9 | 33-27-11 | D02896 | | A1 | | | | TB0162X | B026 | BJ | | 150-199, 275-299 |
| 115 | 20 | | PQ | P | 2-11 | 33-27-11 | D02896 | | B2 | | | | TB0162Y | A016 | BJ | | 050-099 |
| 115 | 20 | | PA | | 2-11 | 33-27-11 | D02896 | | B2 | | | | TB0162Y | A016 | BJ | | 150-199, 275-299 |
| 115Z | | | | P | 0-0 | 33-27-11 | D02896 | | DED | | | | TB0162Y | DED | | | 050-099 |
| 116 | 22 | | PA | | 3-1 | 33-27-11 | D02896 | | X1 | | | | TB0162Z | 9 | BJ | | ALL |
| 117 | 22 | | PA | | 3-5 | 33-27-11 | D02896 | | X2 | | | | D05154J | 26 | | | ALL |
| 120 | 20 | | PA | | 2-0 | 33-24-14 | D05154J | | 18 | | | | TB0162Y | A029 | BJ | | 050-099 |
| 120 | 22 | | PA | | 1-7 | 21-66-31 | D05150J | | 13 | | | | TB0148Y | A034 | BJ | | 150, 152-199 |
| 121 | 20 | | PA | | 2-1 | 33-24-14 | D05108J | | 4 | | | | TB0162Y | A029 | BJ | | 050-099 |
| 122 | 20 | | PA | | 2-0 | 33-24-14 | D05154J | | 17 | | | | TB0162Y | C029 | BJ | | 050-099 |
| 123 | 20 | | PA | | 2-1 | 33-24-14 | D05108J | | 7 | | | | TB0162Y | C029 | BJ | | 050-099 |
| 124 | 22 | | PA | | 1-7 | 33-21-21 | D05154J | | 2 | | | | TB0148Z | 13 | BJ | | ALL |
| 139 | 22 | | PA | | 2-8 | 33-22-42 | D13558 | | 3 | | | | TB0162Z | 38 | BJ | | 050-099 |
| 139 | 22 | | PA | | 3-2 | 33-22-42 | D13558 | | 3 | | | | TB0162Y | A019 | BJ | | 150-199 |
| 152 | 24 | | PK | | 2-4 | 33-21-12 | D05080J | | 10 | | | | TB0148X | A008 | BJ | | 050-099, 150-199 |
| 162 | 22 | | PA | | 2-9 | 33-51-11 | D05086J | | 9 | | | | D05150J | 10 | | | ALL |
| 163 | 22 | | PA | | 2-0 | 33-51-11 | D05084J | | 3 | | | | TB0162X | A025 | BJ | | ALL |
| 201B | 22 | | PB | A | 2-10 | 21-51-22 | D05086J | | 1 | | | | D05080J | 1 | | | ALL |
| 201R | 22 | | PB | A | 0-0 | 21-51-22 | D05086J | | 2 | | | | D05080J | 2 | | | ALL |
| 202B | 24 | | PL | B | 2-10 | 21-61-31 | D05086J | | 3 | | | | D05080J | 4 | | | ALL |
| 202R | 24 | | PL | B | 0-0 | 21-61-31 | D05086J | | 4 | | | | D05080J | 5 | | | ALL |
| 203B | 20 | | PB | C | 2-10 | 21-65-11 | D05144J | | 6 | | | | D05086J | 5 | | | ALL |
| 203R | 20 | | PB | C | 0-0 | 21-65-11 | D05144J | | 7 | | | | D05086J | 6 | | | ALL |
| 204B | 24 | | PL | D | 2-8 | 52-71-11 | D05078J | | 23 | | | | D05086J | 16 | | | ALL |
| 204R | 24 | | PL | D | 0-0 | 52-71-11 | D05078J | | 22 | | | | D05086J | 15 | | | ALL |
| 205B | 24 | | PL | E | 2-8 | 52-71-11 | D05078J | | 25 | | | | D05086J | 18 | | | ALL |
| 205R | 24 | | PL | E | 0-0 | 52-71-11 | D05078J | | 24 | | | | D05086J | 17 | | | ALL |
| 206B | 24 | | PL | F | 2-7 | 52-71-11 | D05078J | | 27 | | | | D05084J | 10 | | | ALL |
| 206R | 24 | | PL | F | 0-0 | 52-71-11 | D05078J | | 26 | | | | D05084J | 9 | | | ALL |
| 207B | 24 | | PL | G | 2-7 | 52-71-11 | D05078J | | 29 | | | | D05084J | 12 | | | ALL |
| 207R | 24 | | PL | G | 0-0 | 52-71-11 | D05078J | | 28 | | | | D05084J | 11 | | | ALL |
| 208B | 22 | | PB | H | 2-11 | 23-31-15 | D05104J | | 2 | | | | D05184J | 2 | | | 050-099 |
| 208R | 22 | | PB | H | 0-0 | 23-31-15 | D05104J | | 1 | | | | D05184J | 1 | | | 050-099 |
| 210B | 22 | | PB | J | 2-9 | 23-31-17 | D05108J | | 2 | | | | D05168J | 2 | | | 050-099 |
| 210R | 22 | | PB | J | 0-0 | 23-31-17 | D05108J | | 1 | | | | D05168J | 1 | | | 050-099 |
| 211B | 22 | | PB | K | 2-2 | 23-31-14 | D05144J | | 4 | | | | TB0162F | C021 | 2 | | ALL |
| 211R | 22 | | PB | K | 0-0 | 23-31-14 | D05144J | | 3 | | | | TB0162F | A021 | 2 | | ALL |
| 212B | 24 | | PL | L | 2-8 | 52-71-11 | D05078J | | 33 | | | | D05086J | 20 | | | ALL |
| 212R | 24 | | PL | L | 0-0 | 52-71-11 | D05078J | | 32 | | | | D05086J | 19 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 23

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1064 | 286T1064 | | | P25 INTEGRATION (continued) | | | | | | | | | | | |
| 213B | 24 | PL | M | 2-7 | 52-71-11 | D05078J | | 35 | | | D05084J | 14 | | | ALL |
| 213R | 24 | PL | M | 0-0 | 52-71-11 | D05078J | | 34 | | | D05084J | 13 | | | ALL |
| 217B | 22 | PB | IQ | 2-9 | 23-31-17 | D05108J | | 5 | | | D05168J | 5 | | | 050-099 |
| 217R | 22 | PB | IQ | 0-0 | 23-31-17 | D05108J | | 6 | | | D05168J | 6 | | | 050-099 |
| 224B | 24 | PL | I | 2-10 | 21-61-71 | D05080J | | 9 | | | D05086J | 21 | | | 050-099 |
| 224B | 24 | PL | X | 2-10 | 21-61-71 | D05080J | | 9 | | | D05086J | 29 | | | 150-199 |
| 224B | 24 | PL | X | 2-10 | 21-61-71 | D05080J | | 9 | | | D05086J | 21 | | | 275-299 |
| 224R | 24 | PL | I | 0-0 | 21-61-71 | D05080J | | 8 | | | D05086J | 22 | | | 050-099 |
| 224R | 24 | PL | X | 0-0 | 21-61-71 | D05080J | | 8 | | | D05086J | 30 | | | 150-199 |
| 224R | 24 | PL | X | 0-0 | 21-61-71 | D05080J | | 8 | | | D05086J | 8 | | | 275-299 |
| 500 | 22 | PA | | 2-4 | 33-22-42 | D00084 | | A3 | | | TB0162X | D023 | BJ | | 050-099 |
| 501 | 22 | PA | | 2-10 | 33-21-21 | D10796 | | D2 | | | TB0148Z | 18 | BJ | | 050-099, 150-199, 280-299 |
| 501 | 22 | PA | | 3-2 | 33-21-21 | D10796 | | D2 | | | TB0148Z | 18 | BJ | | 275-278 |
| 502 | 22 | PA | | 2-11 | 33-21-21 | D10796 | | D1 | | | TB0148Z | 13 | BJ | | 050-099, 150-199, 280-299 |
| 502 | 22 | PA | | 3-3 | 33-21-21 | D10796 | | D1 | | | TB0148Z | 13 | BJ | | 275-278 |
| 503 | 22 | PA | | 1-4 | 33-22-42 | TB0162Y | | C013 | BJ | | D00084 | X1 | | | 050-099 |
| 503 | 22 | PA | | 2-7 | 33-22-42 | D00084 | | X1 | | | TB0162Y | C013 | BJ | | 150-199 |
| 503 | 22 | PA | | 3-3 | 33-22-42 | D10796 | | A1 | | | TB0162Z | 18 | BJ | | 275-278 |
| 503 | 22 | PA | | 2-11 | 33-22-42 | D10796 | | A1 | | | TB0162Z | 18 | BJ | | 280-299 |
| 504 | 22 | PA | | 3-0 | 33-22-42 | D10796 | | A3 | | | TB0162Y | C016 | BJ | | 275-299 |
| 505 | 22 | PA | | 2-11 | 33-22-42 | TB0162Y | | C016 | BJ | | D10796 | C1 | | | 050-099 |
| 505 | 22 | PA | | 3-0 | 33-22-42 | D10796 | | C1 | | | TB0162Y | C016 | BJ | | 150-199 |
| 505 | 22 | PA | | 2-9 | 33-22-42 | D10796 | | B1 | | | TB0162Z | 40 | BJ | | 275-278 |
| 505 | 22 | PA | | 2-5 | 33-22-42 | D10796 | | B1 | | | TB0162Z | 40 | BJ | | 280-299 |
| 506 | 22 | PA | | 2-11 | 33-22-42 | TB0162Y | | C013 | BJ | | D10796 | B3 | | | 050-099 |
| 506 | 22 | PA | | 3-0 | 33-22-42 | D10796 | | B3 | | | TB0162Y | C013 | BJ | | 150-199 |
| 506 | 22 | PA | | 3-3 | 33-22-42 | D10796 | | B2 | | | TB0162Z | 18 | BJ | | 275-278 |
| 506 | 22 | PA | | 2-11 | 33-22-42 | D10796 | | B2 | | | TB0162Z | 18 | BJ | | 280-299 |
| 507 | 22 | PA | | 2-9 | 33-22-42 | D10796 | | B3 | | | TB0162Z | 37 | BJ | | 275-278 |
| 507 | 22 | PA | | 2-5 | 33-22-42 | D10796 | | B3 | | | TB0162Z | 37 | BJ | | 280-299 |
| 510 | 22 | PA | | 3-3 | 33-22-42 | D10796 | | X1 | | | TB0162Z | 18 | BJ | | 275-278 |
| 510 | 22 | PA | | 2-11 | 33-22-42 | D10796 | | X1 | | | TB0162Z | 18 | BJ | | 280-299 |
| 511 | 22 | PA | | 2-6 | 33-22-42 | D05150J | | 24 | | | D10796 | X2 | | | 050-099 |
| 511 | 22 | PA | | 2-5 | 33-22-42 | D10796 | | X2 | | | D05150J | 24 | | | 150-199, 280-299 |
| 511 | 22 | PA | | 2-10 | 33-22-42 | D10796 | | X2 | | | D05150J | 24 | | | 275-278 |
| 512 | 22 | PA | | 3-4 | 33-21-21 | D03640 | | 3 | | | TB0162Y | C014 | BJ | | 050-099 |
| 512 | 22 | PA | | 3-10 | 33-21-21 | D03640 | | 3 | | | TB0162Y | C014 | BJ | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 24

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1064 | 286T1064 | | | P25 INTEGRATION (continued) | | | | | | | | | | | | | | |
| 512 | 22 | | PA | 3-6 | 33-21-21 | D03640 | | | | 3 | | | | TB0162Y | C014 | BJ | | 275-299 |
| 550 | 22 | | PA | 2-5 | 33-22-42 | D10796 | | | | X1 | | | | TB0162Z | 38 | BJ | | 050-099 |
| 550 | 22 | | PA | 2-10 | 33-22-42 | D10796 | | | | X1 | | | | TB0162Y | A019 | BJ | | 150-199 |
| 567 | 22 | | PA | 2-4 | 21-66-31 | D05150J | | | | 14 | | | | TB0162G | 4 | 2 | | 050-099 |
| 567 | 22 | | PA | 2-5 | 21-66-31 | D05150J | | | | 14 | | | | TB0162G | 4 | 2 | | 150, 152-199 |
| 568 | 22 | | PA | 2-5 | 21-66-41 | D05150J | | | | 15 | | | | TB0162G | 6 | 2 | | 050-099 |
| 568 | 22 | | PA | 2-4 | 21-66-41 | D05150J | | | | 15 | | | | TB0162G | 6 | 2 | | 150, 152-199 |
| 569 | 22 | | PA | 1-7 | 21-66-31 | D05150J | | | | 13 | | | | TB0148Y | A034 | BJ | | 050-099 |
| 601 | 22 | | PA | 2-1 | 30-46-11 | TB0162Y | | | | C020 | BJ | | | D05080J | 7 | | | ALL |
| 602 | 22 | | PA | 1-10 | 30-46-11 | TB0162Y | | | | C020 | BJ | | | D05084J | 5 | | | ALL |
| 603 | 22 | | PA | 1-11 | 30-46-11 | TB0162Y | | | | C020 | BJ | | | D05086J | 13 | | | ALL |
| 606 | 22 | | PA | 2-6 | 33-21-21 | D05144J | | | | 9 | | | | TB0148X | A006 | BJ | | 050-099, 150-199 |
| 608 | 24 | | PK | 2-6 | 33-21-21 | D05154J | | | | 4 | | | | TB0148X | B006 | BJ | | 050-099 |
| 608 | 24 | | PK | 1-5 | 33-21-21 | TB0148X | | | | B006 | BJ | | | D05154J | 4 | | | 150-199 |
| 609 | 24 | | PK | 3-2 | 33-21-21 | D03608 | | | | X2 | | | | TB0148X | C006 | BJ | | 050-099, 150-199 |
| 610 | 22 | | PA | 2-7 | 33-22-42 | D13394 | | | | Y1 | | | | TB0148Z | 27 | BJ | | 050-099, 150-199 |
| 611 | 22 | | PA | 2-7 | 33-22-42 | D13394 | | | | X1 | | | | TB0148Z | 27 | BJ | | 050-099, 150-199 |
| 612 | 20 | | PA | 1-7 | 33-22-42 | D05150J | | | | 7 | | | | TB0162Z | 38 | BJ | | 050-099 |
| 612 | 20 | | PA | 2-0 | 33-22-42 | D05150J | | | | 7 | | | | TB0162Y | A019 | BJ | | 150-199 |
| 613 | 20 | | PA | 2-2 | 33-22-42 | D13558 | | | | 1 | | | | GDX0001 | A.. | 2 | | 050-099 |
| 613 | 20 | | PA | 1-7 | 33-22-42 | D13558 | | | | 1 | | | | GDX0001 | A.. | 2 | | 150-199 |
| 614 | 20 | | PA | 2-2 | 33-22-42 | D13558 | | | | 6 | | | | GDX0001 | S.. | 2 | | 050-099 |
| 614 | 20 | | PA | 1-7 | 33-22-42 | D13558 | | | | 6 | | | | GDX0001 | S.. | 2 | | 150-199 |
| 617 | 18 | | PA | 2-4 | 33-27-11 | D02896 | | | | C1 | | | | TB0148G | 40 | 2 | | 150-199 |
| 618 | 18 | | PA | 3-1 | 33-27-11 | D00090 | | | | C1 | | | | TB0162G | 8 | 2 | | 150-199 |
| 619 | 18 | | PA | 2-7 | 33-27-11 | D02896 | | | | C2 | | | | TB0162H | 32 | 2 | | 150-199 |
| 620 | 22 | | PA | 3-5 | 33-22-42 | D13394 | | | | A3 | | | | D05154J | 3 | | | 050-099, 150-199 |
| 621 | 22 | | PA | 3-1 | 33-22-42 | D13394 | | | | A1 | | | | TB0148X | A005 | BJ | | 050-099, 150-199 |
| 622 | 22 | | PA | 3-5 | 33-22-42 | D13394 | | | | B3 | | | | D05154J | 6 | | | 050-099, 150-199 |
| 623 | 22 | | PA | 3-1 | 33-22-42 | D13394 | | | | B1 | | | | TB0148X | B005 | BJ | | 050-099, 150-199 |
| 624 | 22 | | PA | 1-3 | 33-22-42 | D00084 | | | | X2 | | | | D13394 | B2 | | | 050-099, 150-199 |
| 625 | 22 | | PA | 3-0 | 33-22-42 | D13394 | | | | X2 | | | | TB0148Y | A012 | BJ | | 050-099, 150-199 |
| 626 | 24 | | PK | 1-10 | 33-21-12 | D05080J | | | | 11 | | | | TB0148Z | 27 | BJ | | 050-099, 150-199 |
| 627 | 24 | | PK | 2-7 | 33-21-31 | D05144J | | | | 13 | | | | TB0162G | 7 | 2 | | 050-099, 150-199 |
| 629 | 24 | | PK | 1-5 | 33-21-12 | D05154J | | | | 36 | | | | TB0148X | C008 | BJ | | 050-099, 150-199 |
| 630 | 24 | | PK | 1-10 | 33-21-12 | D05154J | | | | 5 | | | | TB0162X | D022 | BJ | | 050-099 |
| 630 | 24 | | PK | 1-5 | 33-21-12 | D05154J | | | | 5 | | | | TB0148X | D008 | BJ | | 150-199 |
| 632 | 18 | | PA | 2-0 | 33-22-31 | D05154J | | | | 1 | | | | TB0162H | 32 | 2 | | 050-099 |
| 632 | 18 | | PA | 2-0 | 33-22-31 | TB0162H | | | | 32 | 2 | | | D05154J | 1 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 25

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1064 | 286T1064 | | | P25 INTEGRATION (continued) | | | | | | | | | | | |
| 637 | 22 | | PA | | 1-8 | 33-21-21 | D05154J | | 39 | | TB0148Z | 18 | BJ | | 050-099 |
| 638 | 22 | | PA | | 1-9 | 33-21-21 | D05084J | | 24 | | TB0148Z | 18 | BJ | | 050-099 |
| 641 | 22 | | PA | | 2-4 | 21-66-41 | D05150J | | 16 | | TB0162G | 5 | 2 | | 050-099, 150, 152-199 |
| 642 | 22 | | PA | | 1-8 | 33-21-21 | TB0148Z | | 18 | BJ | D05154J | 39 | | | 162-199 |
| 652 | 22 | | PA | | 2-8 | 33-22-42 | D72042 | | B1 | | TB0162Y | C019 | BJ | | 280-299 |
| 653 | 22 | | PA | | 2-4 | 33-22-42 | D72042 | | B2 | | D05150J | 20 | | | 280-299 |
| 654 | 22 | | PA | | 2-10 | 33-22-42 | D72042 | | B3 | | TB0162Y | C016 | BJ | | 280-299 |
| 655 | 22 | | PA | | 2-3 | 33-22-42 | D72042 | | X1 | | TB0162Z | 38 | BJ | | 280-299 |
| 656 | 22 | | PA | | 2-4 | 33-22-42 | D72042 | | X2 | | D05150J | 6 | | | 280-299 |
| 700 | 22 | | PA | | 1-9 | 33-22-42 | D12084 | | X1 | | TB0162Z | 37 | BJ | | 275-299 |
| 701 | 22 | | PA | | 1-10 | 33-22-42 | D12084 | | B2 | | D05150J | 21 | | | 275-299 |
| 702 | 22 | | PA | | 1-10 | 33-22-42 | D12084 | | X2 | | D05150J | 22 | | | 275-299 |
| 703 | 22 | | PA | | 2-3 | 33-22-42 | D12084 | | B1 | | TB0162Y | C019 | BJ | | 275-299 |
| 704 | 22 | | PA | | 2-43 | 33-22-42 | D12084 | | B3 | | TB0162Y | C016 | BJ | | 275-299 |
| 705 | 22 | | PA | | 2-7 | 33-22-42 | D00084 | | B3 | | TB0162Y | C016 | BJ | | 275-278 |
| 900 | 22 | | PA | | 1-6 | 33-22-42 | D00084 | | B2 | | TB0148Z | 17 | BJ | | 150, 152-199 |
| 901 | 22 | | PA | | 1-6 | 33-22-42 | D00084 | | B1 | | TB0162Y | C013 | BJ | | 150, 152-199 |
| W1065 | 286T1065 | | | E2-2 SHELF,L ATC BOTTOM ANT COAX | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-53-13 | D00331B | | =C71 | | D04081P | | =C1 | | ALL |
| 01CX | | | | JB A | 4-9 | 34-53-13 | D00331B | | 71 | | D04081P | | =A1 | | ALL |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 | | | | | | | | | | | |
| 001 | 08 | | PA | | 4-0 | 25-53-11 | K00245 | | A2 | E | C00054 | A1 | LA | * | ALL |
| 002 | 08 | | PA | | 4-0 | 25-53-11 | K00245 | | B2 | E | C00054 | B1 | LA | * | ALL |
| 003 | 08 | | PA | | 4-0 | 25-53-11 | K00245 | | C2 | E | C00054 | C1 | LA | * | ALL |
| 004 | 08 | | PA | | 2-0 | 25-53-11 | C00053 | | A1 | D | C00054 | A1 | LA | * | 050-099 |
| 004 | 08 | | PA | | 1-0 | 25-53-11 | C00053 | | A1 | D | C00054 | A1 | LA | * | 150-199, 275-299 |
| 005 | 08 | | PA | | 2-0 | 25-53-11 | C00053 | | B1 | D | C00054 | B1 | LA | * | 050-099 |
| 005 | 08 | | PA | | 1-0 | 25-53-11 | C00053 | | B1 | D | C00054 | B1 | LA | * | 150-199, 275-299 |
| 006 | 08 | | PA | | 2-0 | 25-53-11 | C00053 | | C1 | D | C00054 | C1 | LA | * | 050-099 |
| 006 | 08 | | PA | | 1-0 | 25-53-11 | C00053 | | C1 | D | C00054 | C1 | LA | * | 150-199, 275-299 |
| 007 | 22 | | PA | | 2-0 | 25-53-13 | D01284 | | X1 | | TB0112Z | 27 | BJ | | 050-099 |
| 007 | 08 | | PA | | 6-0 | 25-53-11 | K00245 | | A1 | E | C00015 | 2 | D | | 150-199 |
| 007 | 08 | | PA | | 5-0 | 25-53-11 | K00245 | | A1 | E | C00015 | 2 | D | | 275-299 |
| 008 | 12 | | PA | | 4-0 | 25-53-11 | C00053 | | B2 | D | C00049 | 2 | D | * | 050-099 |
| 008 | 12 | | PA | | 3-0 | 25-53-11 | C00053 | | B2 | D | C00049 | 2 | D | * | 150-199, 275-299 |
| 009 | 22 | | PA | | 6-0 | 25-53-13 | TB0114D | | C | 2 | S00384 | 8 | C | * | 050-099 |
| 009 | 22 | | PA | | 6-0 | 25-53-13 | TB0114D | | C003 | 2 | L00826 | =G | \$ | * | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1060
Page 26
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|----------|---------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | |
| 010 | 22 | PA | | 6-0 | 25-53-13 | TB0114D | | C | 2 | | S00384 | 11 | C | | 050-099 |
| 010 | 22 | PA | | 6-0 | 25-53-13 | TB0110Z | | | 21 | BJ | L00812 | =G | \$ | | 150-199, 275-299 |
| 011 | 12 | PA | | 3-0 | 25-53-11 | C00053 | | A2 | D | | C00085 | A1 | D | * | 050-099 |
| 011 | 12 | PA | | 3-0 | 25-53-11 | C00053 | | A2 | D | | C00170 | A1 | D | * | 150-199, 275-299 |
| 012 | 12 | PA | | 2-0 | 25-53-11 | C00085 | | A1 | D | * | C00086 | A1 | D | * | 050-099 |
| 012 | 12 | PA | | 1-0 | 25-53-11 | C00170 | | A1 | D | * | C00171 | A1 | D | * | 150-199, 275-299 |
| 013 | 12 | PA | | 3-0 | 25-53-11 | C00086 | | A1 | D | * | C00087 | A1 | D | * | 050-099 |
| 013 | 12 | PA | | 1-0 | 25-53-11 | C00171 | | A1 | D | * | C00172 | A1 | D | * | 150-199, 275-299 |
| 014 | 12 | PA | | 3-0 | 25-53-11 | C00087 | | A1 | D | * | C00088 | A1 | D | | 050-099 |
| 014 | 12 | PA | | 1-0 | 25-53-11 | C00172 | | A1 | D | * | C00173 | A1 | D | | 150-199, 275-299 |
| 015 | 12 | PA | | 3-0 | 25-53-11 | C00054 | | A2 | D | | C00081 | A2 | D | * | 050-099 |
| 015 | 12 | PA | | 2-0 | 25-53-11 | C00054 | | A2 | D | | C00166 | A2 | D | * | 150-199, 275-299 |
| 016 | 12 | PA | | 2-0 | 25-53-11 | C00081 | | A2 | D | * | C00082 | A2 | D | * | 050-099 |
| 016 | 12 | PA | | 1-0 | 25-53-11 | C00166 | | A2 | D | * | C00167 | A2 | D | * | 150-199, 275-299 |
| 017 | 12 | PA | | 2-0 | 25-53-11 | C00082 | | A2 | D | * | C00083 | A2 | D | * | 050-099 |
| 017 | 12 | PA | | 1-0 | 25-53-11 | C00167 | | A2 | D | * | C00168 | A2 | D | * | 150-199, 275-299 |
| 018 | 12 | PA | | 2-0 | 25-53-11 | C00083 | | A2 | D | * | C00084 | A2 | D | | 050-099 |
| 018 | 12 | PA | | 1-0 | 25-53-11 | C00168 | | A2 | D | * | C00169 | A2 | D | | 150-199, 275-299 |
| 019 | 22 | PA | | 5-0 | 25-53-13 | TB0110D | | C037 | 2 | | TB0114D | C | 2 | | 050-099 |
| 019 | 22 | PA | | 2-0 | 25-53-13 | TB0114D | | C012 | 2 | | TB0114D | C011 | 2 | | 150-199, 275-299 |
| 01A | 22 | PA | | 7-0 | 25-53-13 | L00436 | | =P | \$ | | TB0110H | 16 | 2 | | 150-199, 275-299 |
| 01B | 22 | PA | | 5-0 | 25-53-13 | TB0110H | | 16 | 2 | | D05216J | 9 | | | 150-199, 275-299 |
| 01C | 22 | PA | | 6-0 | 25-53-13 | L00436 | | =G | \$ | | TB0110Z | 39 | BJ | | 150-199, 275-299 |
| 01D | 22 | PA | | 6-0 | 25-53-13 | TB0110Z | | 50 | BJ | | TB0306Z | 9 | BJ | | 150-199, 275-299 |
| 01E | 22 | PA | | 4-0 | 25-53-13 | D01288 | | X2 | | | TB0110Z | 50 | BJ | | 150-199, 275-299 |
| 01F | 22 | PA | | 2-0 | 25-53-14 | D11632 | | 3 | | | TB0110H | 39 | 2 | | 050-099 |
| 01F | 22 | PA | | 3-0 | 25-53-13 | D11632 | | 3 | | | TB0110Z | 50 | BJ | | 150-199, 275-299 |
| 01G | 22 | PA | | 7-0 | 25-53-13 | TB0110H | | 16 | 2 | | S00563 | 4 | C | | 150-199, 275-299 |
| 01H | 22 | PA | | 5-0 | 25-53-13 | D11630 | | 6 | | | TB0110H | 16 | 2 | | 150-199, 275-299 |
| 01J | 22 | PA | | 7-0 | 25-53-13 | D11630 | | 12 | | | TB0306Z | 8 | BJ | | 150-199, 275-299 |
| 01K | 22 | PA | | 2-0 | 25-53-13 | D01284 | | 2 | | | TB0110G | 32 | 2 | | 150-199, 275-299 |
| 01L | 22 | PA | | 2-0 | 25-53-13 | D01284 | | 3 | | | TB0110Z | 41 | BJ | | 150-199, 275-299 |
| 01M | 22 | PA | | 4-0 | 25-53-13 | D05216J | | 13 | | | TB0110G | 32 | 2 | | 150-199, 275-299 |
| 01N | 22 | PA | | 5-0 | 25-53-13 | TB0110Z | | 39 | BJ | | S00698 | 5 | B | | 150-199, 275-299 |
| 01P | 22 | PA | | 5-0 | 25-53-13 | TB0110Z | | 51 | BJ | | S00698 | 2 | B | * | 150-199, 275-299 |
| 01Q | 22 | PA | | 4-0 | 25-53-13 | TB0114D | | C008 | 2 | | TB0110Z | 51 | BJ | | 150-199, 275-299 |
| 01R | 22 | PA | | 2-0 | 25-53-13 | TB0114D | | C008 | 2 | | TB0114D | C007 | 2 | | 150-199, 275-299 |
| 01S | 22 | PA | | 7-0 | 25-53-13 | S00563 | | 8 | C | | TB0110H | 10 | 2 | | 150-199, 275-299 |
| 01T | 22 | PA | | 3-0 | 25-53-13 | D01284 | | 5 | | | D02438 | X1 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 27

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | |
| 01U | 22 | PA | | | 3-0 | 25-53-13 | D01284 | | 7 | | TB0110H | 16 | 2 | | 150-199, 275-299 |
| 01V | 22 | PA | | | 5-0 | 25-53-14 | TB0110G | | 22 | 2 | D11630 | | 1 | | 150-199, 275-299 |
| 01X | 22 | PA | | | 4-0 | 25-53-14 | D11630 | | 2 | | D05224J | | 33 | | 050-099 |
| 01X | 22 | PA | | | 5-0 | 25-53-14 | TB0110G | | 24 | 2 | D11630 | | 2 | | 150-199, 275-299 |
| 021 | 12 | PA | | | 3-0 | 25-53-11 | C00053 | | B2 | D | C00085 | | B1 | D | * 050-099 |
| 021 | 12 | PA | | | 3-0 | 25-53-11 | C00053 | | B2 | D | C00170 | | B1 | D | * 150-199, 275-299 |
| 022 | 12 | PA | | | 2-0 | 25-53-11 | C00085 | | B1 | D | C00086 | | B1 | D | * 050-099 |
| 022 | 12 | PA | | | 1-0 | 25-53-11 | C00170 | | B1 | D | C00171 | | B1 | D | * 150-199, 275-299 |
| 023 | 12 | PA | | | 2-0 | 25-53-11 | C00086 | | B1 | D | C00087 | | B1 | D | * 050-099 |
| 023 | 12 | PA | | | 1-0 | 25-53-11 | C00171 | | B1 | D | C00172 | | B1 | D | * 150-199, 275-299 |
| 024 | 12 | PA | | | 2-0 | 25-53-11 | C00087 | | B1 | D | C00088 | | B1 | D | 050-099 |
| 024 | 12 | PA | | | 1-0 | 25-53-11 | C00172 | | B1 | D | C00173 | | B1 | D | 150-199, 275-299 |
| 025 | 12 | PA | | | 3-0 | 25-53-11 | C00054 | | B2 | D | C00081 | | B2 | D | * 050-099 |
| 025 | 12 | PA | | | 2-0 | 25-53-11 | C00054 | | B2 | D | C00166 | | B2 | D | * 150-199, 275-299 |
| 026 | 12 | PA | | | 2-0 | 25-53-11 | C00081 | | B2 | D | C00082 | | B2 | D | * 050-099 |
| 026 | 12 | PA | | | 1-0 | 25-53-11 | C00166 | | B2 | D | C00167 | | B2 | D | * 150-199, 275-299 |
| 027 | 12 | PA | | | 2-0 | 25-53-11 | C00082 | | B2 | D | C00083 | | B2 | D | * 050-099 |
| 027 | 12 | PA | | | 1-0 | 25-53-11 | C00167 | | B2 | D | C00168 | | B2 | D | * 150-199, 275-299 |
| 028 | 12 | PA | | | 2-0 | 25-53-11 | C00083 | | B2 | D | C00084 | | B2 | D | 050-099 |
| 028 | 12 | PA | | | 1-0 | 25-53-11 | C00168 | | B2 | D | C00169 | | B2 | D | 150-199, 275-299 |
| 02A | 22 | PA | | | 5-0 | 25-53-14 | D05224J | | 36 | | D01288 | | C3 | | 150-199, 275-299 |
| 02B | 22 | PA | | | 2-0 | 25-53-14 | D02478 | | 6 | | TB0110Z | | 43 | BJ | 150-199, 275-299 |
| 02C | 22 | PA | | | 1-0 | 25-53-14 | D02478 | | 8 | | D01518 | | 6 | | 150-199, 275-299 |
| 02D | 22 | PA | | | 3-0 | 25-53-14 | D01518 | | 8 | | TB0110Z | | 34 | BJ | 150-199, 275-299 |
| 02E | 22 | PA | | | 5-0 | 25-53-14 | D05224J | | 39 | | TB0110Z | | 34 | BJ | 150-199, 275-299 |
| 02G | 22 | PA | | | 2-0 | 25-53-16 | D01288 | | D3 | | D11624 | | 12 | | 050-099 |
| 02G | 22 | PA | | | 7-0 | 25-53-14 | TB0306Y | A006 | BJ | | D11624 | | 7 | | 150-199, 275-299 |
| 02H | 22 | PA | | | 4-0 | 25-53-14 | D01288 | | C2 | | TB0110Y | C052 | BJ | | 150-199, 275-299 |
| 02J | 22 | PA | | | 7-0 | 25-53-16 | D11624 | | 7 | | TB0306Y | A006 | BJ | | 050-099 |
| 02J | 22 | PA | | | 1-0 | 25-53-14 | D01288 | | D3 | | D11624 | | 12 | | 150-199, 275-299 |
| 02K | 22 | PA | | | 2-0 | 25-53-16 | D11624 | | 11 | | TB0112Y | C012 | BJ | | 050-099 |
| 02K | 22 | PA | | | 3-0 | 25-53-14 | D11624 | | 11 | | TB0110Y | C052 | BJ | | 150-199, 275-299 |
| 02L | 22 | PA | | | 3-0 | 25-53-14 | D02456 | | C1 | | TB0110Z | | 43 | BJ | 150-199, 275-299 |
| 02N | 22 | PA | | | 4-0 | 25-53-14 | D11630 | | 9 | | TB0110Z | | 34 | BJ | 150-199, 275-299 |
| 02P | 22 | PA | | | 4-0 | 25-53-14 | D11630 | | 10 | | TB0110Y | A052 | BJ | | 150-199, 275-299 |
| 02Q | 22 | PA | | | 6-0 | 25-53-14 | D11632 | | 2 | | TB0306Y | C004 | BJ | | 050-099 |
| 02Q | 22 | PA | | | 5-0 | 25-53-14 | D11632 | | 2 | | TB0110Y | A052 | BJ | | 150-199, 275-299 |
| 02R | 22 | PA | | | 5-0 | 25-53-14 | D05224J | | 43 | | D02456 | | D2 | | 150-199, 275-299 |
| 02S | 22 | PA | | | 4-0 | 25-53-14 | D02456 | | D1 | | TB0110Y | C053 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 28

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 02T | 22 | | PA | 4-0 | 25-53-14 | D01288 | A1 | | | | | | TB0110Y | C053 | BJ | | 150-199, 275-299 |
| 02U | 22 | | PA | 4-0 | 25-53-14 | D01288 | D2 | | | | | | TB0110Z | 42 | BJ | | 150-199, 275-299 |
| 02V | 22 | | PA | 6-0 | 25-53-14 | D05224J | 41 | | | | | | D01288 | B1 | | | 150-199, 275-299 |
| 02W | 22 | | PA | 5-0 | 25-53-14 | D11630 | 11 | | | | | | D05224J | 42 | | | 150-199, 275-299 |
| 02X | 22 | | PA | 4-0 | 25-53-14 | D05224J | 45 | | | | | | TB0110Y | C053 | BJ | | 150-199, 275-299 |
| 031 | 12 | | PA | 3-0 | 25-53-11 | C00053 | C2 | D | | | | | C00085 | C1 | D | * | 050-099 |
| 031 | 12 | | PA | 3-0 | 25-53-11 | C00053 | C2 | D | | | | | C00170 | C1 | D | * | 150-199, 275-299 |
| 032 | 12 | | PA | 2-0 | 25-53-11 | C00085 | C1 | D | * | | | | C00086 | C1 | D | * | 050-099 |
| 032 | 12 | | PA | 1-0 | 25-53-11 | C00170 | C1 | D | * | | | | C00171 | C1 | D | * | 150-199, 275-299 |
| 033 | 12 | | PA | 2-0 | 25-53-11 | C00086 | C1 | D | * | | | | C00087 | C1 | D | * | 050-099 |
| 033 | 12 | | PA | 1-0 | 25-53-11 | C00171 | C1 | D | * | | | | C00172 | C1 | D | * | 150-199, 275-299 |
| 034 | 12 | | PA | 2-0 | 25-53-11 | C00087 | C1 | D | * | | | | C00088 | C1 | D | | 050-099 |
| 034 | 12 | | PA | 1-0 | 25-53-11 | C00172 | C1 | D | * | | | | C00173 | C1 | D | | 150-199, 275-299 |
| 035 | 12 | | PA | 3-0 | 25-53-11 | C00054 | C2 | D | | | | | C00081 | C2 | D | * | 050-099 |
| 035 | 12 | | PA | 2-0 | 25-53-11 | C00054 | C2 | D | | | | | C00166 | C2 | D | * | 150-199, 275-299 |
| 036 | 12 | | PA | 2-0 | 25-53-11 | C00081 | C2 | D | * | | | | C00082 | C2 | D | * | 050-099 |
| 036 | 12 | | PA | 1-0 | 25-53-11 | C00166 | C2 | D | * | | | | C00167 | C2 | D | * | 150-199, 275-299 |
| 037 | 12 | | PA | 2-0 | 25-53-11 | C00082 | C2 | D | * | | | | C00083 | C2 | D | * | 050-099 |
| 037 | 12 | | PA | 1-0 | 25-53-11 | C00167 | C2 | D | * | | | | C00168 | C2 | D | * | 150-199, 275-299 |
| 038 | 12 | | PA | 2-0 | 25-53-11 | C00083 | C2 | D | * | | | | C00084 | C2 | D | | 050-099 |
| 038 | 12 | | PA | 1-0 | 25-53-11 | C00168 | C2 | D | * | | | | C00169 | C2 | D | | 150-199, 275-299 |
| 03A | 22 | | PA | 4-0 | 25-53-14 | D01288 | B2 | | | | | | TB0112Z | 25 | BJ | | 150-199, 275-299 |
| 03B | 22 | | PA | 3-0 | 25-53-16 | D11624 | 10 | | | | | | TB0110H | 43 | 2 | | 050-099 |
| 03B | 22 | | PA | 4-0 | 25-53-14 | D11624 | 10 | | | | | | TB0110Z | 43 | BJ | | 150-199, 275-299 |
| 03C | 22 | | PA | 6-0 | 25-53-16 | D01284 | B3 | | | | | | TB0306Y | C001 | BJ | | 050-099 |
| 03C | 22 | | PA | 6-0 | 25-53-16 | D01284 | 8 | | | | | | TB0306Y | C001 | BJ | | 150-199, 275-299 |
| 03D | 22 | | PA | 3-0 | 25-53-16 | D01284 | B2 | | | | | | TB0110G | 38 | 2 | | 050-099 |
| 03D | 22 | | PA | 4-0 | 25-53-16 | D01284 | 6 | | | | | | TB0110G | 29 | 2 | | 150-199, 275-299 |
| 03E | 22 | | PA | 2-0 | 25-53-16 | D11850 | 3 | | | | | | TB0112Z | 26 | BJ | | 050-099 |
| 03E | 22 | | PA | 3-0 | 25-53-16 | D11850 | 3 | | | | | | TB0110Z | 38 | BJ | | 150-199, 275-299 |
| 03G | 22 | | PA | 2-0 | 25-53-16 | D11850 | 4 | | | | | | TB0110G | 38 | 2 | | 050-099 |
| 03G | 22 | | PA | 4-0 | 25-53-16 | D11850 | 4 | | | | | | TB0110G | 29 | 2 | | 150-199, 275-299 |
| 03L | 22 | | PA | 5-0 | 25-53-16 | D11850 | 7 | | | | | | TB0306Y | C002 | BJ | | 050-099 |
| 03L | 22 | | PA | 4-0 | 25-53-16 | D11850 | 7 | | | | | | TB0110G | 26 | 2 | | 150-199, 275-299 |
| 03M | 22 | | PA | 2-0 | 25-53-16 | D11850 | 2 | | | | | | TB0112Y | A012 | BJ | | 050-099 |
| 03M | 22 | | PA | 3-0 | 25-53-16 | D11850 | 2 | | | | | | TB0110Z | 44 | BJ | | 150-199, 275-299 |
| 03Q | 22 | | PA | 7-0 | 25-53-16 | D11620 | 7 | | | | | | TB0306Z | 13 | BJ | | ALL |
| 03R | 22 | | PA | 2-0 | 25-53-16 | D11620 | 3 | | | | | | TB0112Z | 26 | BJ | | 050-099 |
| 03R | 22 | | PA | 3-0 | 25-53-16 | D11620 | 3 | | | | | | TB0110Z | 42 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 29

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 03S | 22 | | PA | 5-0 | 25-53-16 | D11626 | | 4 | | | | | TB0306Z | 13 | BJ | | 050-099 |
| 03S | 22 | | PA | 7-0 | 25-53-16 | D11626 | | 4 | | | | | TB0306Z | 13 | BJ | | 150-199, 275-299 |
| 03U | 22 | | PA | 2-0 | 25-53-16 | D11626 | | 7 | | | | | TB0110G | 30 | 2 | | 050-099 |
| 03U | 22 | | PA | 3-0 | 25-53-16 | D11626 | | 7 | | | | | TB0110G | 32 | 2 | | 150-199, 275-299 |
| 03V | 22 | | PA | 2-0 | 25-53-16 | D11626 | | 3 | | | | | TB0112Z | 26 | BJ | | 050-099 |
| 03V | 22 | | PA | 7-0 | 25-53-16 | D11626 | | 3 | | | | | TB0306Z | 9 | BJ | | 150-199, 275-299 |
| 03W | 22 | | PA | 3-0 | 25-53-16 | D11628 | | 12 | | | | | TB0112Z | 26 | BJ | | 050-099 |
| 03W | 22 | | PA | 7-0 | 25-53-16 | D11628 | | 12 | | | | | TB0306Z | 9 | BJ | | 150-199, 275-299 |
| 03X | 22 | | PA | 4-0 | 25-53-16 | D11628 | | 6 | | | | | TB0110G | 13 | 2 | | 050-099 |
| 03X | 22 | | PA | 2-0 | 25-53-16 | D11628 | | 6 | | | | | TB0110Y | A053 | BJ | | 150-199, 275-299 |
| 041 | 18 | | PA | 3-0 | 33-37-11 | D05886J | | 13 | DK | | | | D05614J | 14 | | | 050-099 |
| 041 | 18 | | PA | 2-0 | 33-37-11 | D05886J | | 13 | DK | | | | D05614J | 14 | | | 150-199, 275-299 |
| 042 | 20 | | PA | 5-0 | 33-37-11 | D05886J | | 14 | | | | | S00402 | 1 | C | | 050-099 |
| 042 | 18 | | PA | 4-0 | 33-37-11 | D05886J | | 14 | DK | | | | S00402 | 1 | C | | 150-199, 275-299 |
| 043 | 18 | | PA | 5-0 | 33-37-11 | D05886J | | 15 | DK | | | | S00402 | 3 | C | | 050-099 |
| 043 | 18 | | PA | 4-0 | 33-37-11 | D05886J | | 15 | DK | | | | S00402 | 3 | C | | 150-199, 275-299 |
| 044 | 18 | | PA | 2-0 | 33-37-11 | D02632 | | A1 | | | | | TB0112G | 20 | 2 | | 050-099 |
| 044 | 18 | | PA | 4-0 | 33-37-11 | D02632 | | A1 | | | | | TB0112G | 20 | 2 | | 150-199, 275-299 |
| 046 | 18 | | PA | 5-0 | 33-37-11 | S00402 | | 2 | C | | | | TB0112G | 20 | 2 | | ALL |
| 049 | 18 | | PA | 3-0 | 33-37-11 | T00148 | | HV1 | E | | * | | D05614J | 16 | | | 050-099 |
| 049 | 16 | | PA | 3-0 | 33-37-11 | T00148 | | HV1 | E | | * | | D05614J | 16 | | | 150-199, 275-299 |
| 04A | 22 | | PA | 2-0 | 25-53-16 | D11628 | | 11 | | | | | TB0112Y | A013 | BJ | | 050-099 |
| 04A | 22 | | PA | 3-0 | 25-53-16 | D11628 | | 11 | | | | | TB0112Z | 26 | BJ | | 150-199, 275-299 |
| 04B | 22 | | PA | 4-0 | 25-53-16 | D11628 | | 7 | | | | | TB0110G | 26 | 2 | | 050-099 |
| 04B | 22 | | PA | 3-0 | 25-53-16 | D11628 | | 7 | | | | | TB0112Z | 25 | BJ | | 150-199, 275-299 |
| 04C | 22 | | PA | 7-0 | 25-53-16 | TB0112D | | C018 | 2 | | | | TB0306Z | 13 | BJ | | 150-199, 275-299 |
| 04D | 22 | | PA | 4-0 | 25-53-16 | TB0110H | | 16 | 2 | | | | TB0112D | A018 | 2 | | 150-199, 275-299 |
| 04G | 22 | | PA | 2-0 | 25-53-16 | D11626 | | 6 | | | | | TB0112Y | A012 | BJ | | 050-099 |
| 04G | 22 | | PA | 4-0 | 25-53-16 | D11626 | | 6 | | | | | TB0110Z | 44 | BJ | | 150-199, 275-299 |
| 04H | 22 | | PA | 6-0 | 25-53-16 | D11628 | | 14 | | | | | TB0306Y | C002 | BJ | | 050-099 |
| 04H | 22 | | PA | 3-0 | 25-53-16 | D11628 | | 14 | | | | | TB0110G | 26 | 2 | | 150-199, 275-299 |
| 04J | 22 | | PA | 2-0 | 25-53-16 | D11626 | | 2 | | | | | TB0112D | C022 | 2 | | 050-099 |
| 04J | 22 | | PA | 4-0 | 25-53-16 | D11626 | | 2 | | | | | TB0112D | C022 | 2 | | 150-199, 275-299 |
| 04K | 22 | | PA | 2-0 | 25-53-16 | D11628 | | 10 | | | | | TB0112D | A022 | 2 | | 050-099 |
| 04K | 22 | | PA | 3-0 | 25-53-16 | D11628 | | 10 | | | | | TB0112D | A022 | 2 | | 150-199, 275-299 |
| 04L | 22 | | PA | 5-0 | 25-53-14 | D11630 | | 8 | | | | | TB0112Y | A012 | BJ | | 150-199, 275-299 |
| 04M | 22 | | PA | 2-0 | 25-53-16 | D11624 | | 6 | | | | | TB0112D | C018 | 2 | | 050-099 |
| 04M | 22 | | PA | 4-0 | 25-53-14 | D11624 | | 6 | | | | | TB0112D | C004 | 2 | | 150-199, 275-299 |
| 04N | 22 | | PA | 2-0 | 25-53-16 | D11624 | | 8 | | | | | TB0112D | C018 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 30

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 04N | 22 | PA | | | 4-0 | 25-53-14 | D11624 | | 8 | | | | TB0112D | C004 | 2 | | 150-199, 275-299 |
| 04P | 22 | PA | | | 2-0 | 25-53-16 | D11626 | | 1 | | | | TB0110G | 38 | 2 | | 050-099 |
| 04P | 22 | PA | | | 4-0 | 25-53-16 | D11626 | | 1 | | | | TB0110G | 29 | 2 | | 150-199, 275-299 |
| 04Q | 22 | PA | | | 7-0 | 25-53-13 | TB0110H | | 12 | 2 | | | S00563 | 9 | C | | 150-199, 275-299 |
| 04R | 22 | PA | | | 7-0 | 25-53-13 | S00698 | | 1 | B | | | TB0110H | 12 | 2 | | 150-199, 275-299 |
| 04S | 22 | PA | | | 1-0 | 25-53-13 | S00677 | | 4 | B | * | | S00698 | 4 | B | | 150-199, 275-299 |
| 04T | 22 | PA | | | 2-0 | 25-53-16 | D01288 | | | D2 | | | TB0112Z | 26 | BJ | | 050-099 |
| 04T | 22 | PA | | | 4-0 | 25-53-14 | D02438 | | | C2 | | | TB0110Z | 43 | BJ | | 150-199, 275-299 |
| 04U | 22 | PA | | | 5-0 | 25-53-15 | TB0110H | | 16 | 2 | | | TB0114D | A005 | 2 | | 150-199, 275-299 |
| 04V | 22 | PA | | | 1-0 | 25-53-15 | TB0114D | | | C005 | 2 | | TB0114D | C006 | 2 | | 150-199, 275-299 |
| 04W | 22 | PA | | | 4-0 | 25-53-15 | D02460 | | | X1 | | | TB0114D | C006 | 2 | | 150-199, 275-299 |
| 04X | 22 | PA | | | 1-0 | 25-53-14 | D02476 | | | 6 | | | TB0110Z | 7 | BJ | | 150-199, 275-299 |
| 050 | 18 | PA | | | 6-0 | 33-37-11 | T00148 | | | HV1 | E | * | D02632 | A2 | | | 050-099 |
| 050 | 16 | PA | | | 5-0 | 33-37-11 | T00148 | | | HV1 | E | * | D02632 | A2 | | | 150-199, 275-299 |
| 051 | 12 | PA | | | 4-0 | 33-37-11 | T00148 | | | GND | E | | D05614J | 18 | | | 050-099 |
| 051 | 12 | PA | | | 3-0 | 33-37-11 | T00148 | | | GND | E | | D05614J | 18 | | | 150-199, 275-299 |
| 052 | 12 | PA | | | 6-0 | 33-37-11 | T00148 | | | LV | E | | C00021 | 2 | D | | ALL |
| 053 | 18 | PA | | | 5-0 | 33-37-11 | C00021 | | | 1 | D | | D04304J | 19 | | | 050-099 |
| 053 | 16 | PA | | | 4-0 | 33-37-11 | C00021 | | | 1 | D | | D04304J | 19 | | | 150-199, 275-299 |
| 054 | 18 | PA | | | 5-0 | 33-37-11 | C00022 | | | 1 | D | | D04304J | 23 | | | 050-099 |
| 054 | 16 | PA | | | 4-0 | 33-37-11 | C00022 | | | 1 | D | | D04304J | 23 | | | 150-199, 275-299 |
| 055 | 20 | PA | | | 6-0 | 33-37-11 | C00023 | | | 1 | D | | D02528 | A1 | | | 050-099 |
| 055 | 18 | PA | | | 5-0 | 33-37-11 | C00023 | | | 1 | D | | D02528 | A1 | | | 150-199, 275-299 |
| 056 | 20 | PA | | | 4-0 | 33-37-11 | D04304J | | | 20 | | | D02528 | A2 | | | 050-099 |
| 056 | 18 | PA | | | 4-0 | 33-37-11 | D04304J | | | 15 | | | D02528 | A2 | | | 150-199, 275-299 |
| 057 | 20 | PA | | | 4-0 | 33-31-61 | C00015 | | | 1 | D | | D05886J | 11 | | | 050-099 |
| 057 | 20 | PA | | | 5-0 | 33-31-61 | C00015 | | | 1 | D | | D05886J | 11 | | | 150-199, 275-299 |
| 058 | 20 | PA | | | 3-0 | 33-31-61 | T00186 | | | HV1 | E | | D05886J | 12 | | | 050-099, 275-299 |
| 058 | 20 | PA | | | 4-0 | 33-31-61 | T00186 | | | HV1 | E | | D05886J | 12 | | | 150-199 |
| 059 | 16 | PA | | | 3-0 | 33-31-61 | T00186 | | | GND | E | | D05614J | 20 | | | 050-099 |
| 059 | 16 | PA | | | 4-0 | 33-31-61 | D05614J | | | 20 | | | T00186 | GND | E | | 150-199 |
| 059 | 16 | PA | | | 3-0 | 33-31-61 | D05614J | | | 20 | | | T00186 | GND | E | | 275-299 |
| 05A | 22 | PA | | | 1-0 | 25-53-13 | TB0110Z | | | 38 | BJ | | TB0110Z | 42 | BJ | | 150-199, 275-299 |
| 05D | 22 | PA | | | 3-0 | 25-53-17 | TB0112G | | | 27 | 2 | | TB0110Z | 38 | BJ | | 150-199, 275-299 |
| 060 | 16 | PA | | | 6-0 | 33-31-61 | T00186 | | | LV | E | | C00012 | 2 | D | | 050-099 |
| 060 | 16 | PA | | | 6-0 | 33-31-61 | C00012 | | | 2 | D | | T00186 | LV | E | | 150-199, 275-299 |
| 061 | 20 | PA | | | 6-0 | 33-31-61 | C00016 | | | 1 | D | | D02528 | B1 | | | ALL |
| 062 | 20 | PA | | | 4-0 | 33-31-61 | D04304J | | | 17 | | | D02528 | B2 | | | 050-099 |
| 062 | 20 | PA | | | 5-0 | 33-31-61 | D02528 | | | B2 | | | D04304J | 17 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 31

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | |
| 063 | 20 | PA | | | 5-0 | 33-31-61 | C00018 | | 1 | D | | | | | | 050-099 |
| 063 | 20 | PA | | | 5-0 | 33-31-61 | D04304J | | 18 | | | | | | | 150-199 |
| 063 | 20 | PA | | | 6-0 | 33-31-61 | D04304J | | 18 | | | | | | | 275-299 |
| 064 | 18 | PA | | | 3-0 | 33-37-11 | D02528 | | C1 | | | | | | | 050-099 |
| 064 | 16 | PA | | | 3-0 | 33-37-11 | D02528 | | C1 | | | | | | | 150-199, 275-299 |
| 065 | 18 | PA | | | 6-0 | 33-37-11 | D02528 | | C2 | | | | | | | 050-099 |
| 065 | 16 | PA | | | 5-0 | 33-37-11 | D02528 | | C2 | | | | | | * | 150-199, 275-299 |
| 071 | 22 | PA | | | 2-0 | 25-53-15 | TB0112H | | 7 | 2 | | | | | | 050-099 |
| 071 | 22 | PA | | | 4-0 | 25-53-15 | TB0112Z | | 7 | BJ | | | | | | 150-199, 275-299 |
| 072 | 22 | PA | | | 2-0 | 25-53-15 | TB0112H | | 7 | 2 | | | | | | 050-099 |
| 072 | 22 | PA | | | 4-0 | 25-53-15 | TB0112Z | | 7 | BJ | | | | | | 150-199, 275-299 |
| 073 | 22 | PA | | | 2-0 | 25-53-15 | TB0112H | | 7 | 2 | | | | | | 050-099 |
| 073 | 22 | PA | | | 4-0 | 25-53-15 | TB0112Z | | 7 | BJ | | | | | | 150-199, 275-299 |
| 075 | 20 | PA | | | 6-0 | 33-31-61 | C00012 | | 1 | D | | | | | | ALL |
| 076 | 20 | PA | | | 4-0 | 33-31-61 | D04304J | | 22 | | | | | | | 050-099 |
| 076 | 20 | PA | | | 5-0 | 33-31-61 | D02528 | | D2 | | | | | | | 150-199, 275-299 |
| 081 | 22 | PA | | | 2-0 | 25-53-15 | TB0112H | | 7 | 2 | | | | | | 050-099 |
| 081 | 22 | PA | | | 4-0 | 25-53-15 | TB0112Z | | 7 | BJ | | | | | | 150-199, 275-299 |
| 082 | 22 | PA | | | 2-0 | 25-53-15 | TB0112H | | 7 | 2 | | | | | | 050-099 |
| 082 | 22 | PA | | | 4-0 | 25-53-15 | TB0112Z | | 7 | BJ | | | | | | 150-199, 275-299 |
| 083 | 22 | PA | | | 2-0 | 25-53-15 | TB0112H | | 7 | 2 | | | | | | 050-099 |
| 083 | 22 | PA | | | 4-0 | 25-53-15 | TB0112Z | | 7 | BJ | | | | | | 150-199, 275-299 |
| 092 | 22 | PA | | | 3-0 | 25-53-16 | D02454 | | C2 | | | | | | | 050-099 |
| 092 | 22 | PA | | | 4-0 | 25-53-16 | D02454 | | C2 | | | | | | | 150-199, 275-299 |
| 093 | 22 | PA | | | 3-0 | 25-53-16 | D02454 | | D2 | | | | | | | 050-099 |
| 093 | 22 | PA | | | 4-0 | 25-53-16 | D02454 | | D2 | | | | | | | 150-199, 275-299 |
| 094 | 22 | PA | | | 3-0 | 25-53-16 | D02456 | | A2 | | | | | | | 050-099 |
| 094 | 22 | PA | | | 4-0 | 25-53-16 | D02456 | | A2 | | | | | | | 150-199, 275-299 |
| 095 | 22 | PA | | | 3-0 | 25-53-16 | D02456 | | B2 | | | | | | | 050-099 |
| 095 | 22 | PA | | | 4-0 | 25-53-16 | D02456 | | B2 | | | | | | | 150-199, 275-299 |
| 096 | 22 | PA | | | 3-0 | 25-53-17 | TB0112H | | 1 | 2 | | | | | | 050-099 |
| 096 | 22 | PA | | | 2-0 | 25-53-17 | TB0112Z | | 2 | BJ | | | | | | 150-199, 275-299 |
| 097 | 22 | PA | | | 3-0 | 25-53-17 | D02462 | | B2 | | | | | | | 050-099 |
| 097 | 22 | PA | | | 3-0 | 25-53-17 | TB0112Z | | 2 | BJ | | | | | | 150-199, 275-299 |
| 098 | 22 | PA | | | 3-0 | 25-53-17 | D02462 | | A2 | | | | | | | 050-099 |
| 098 | 22 | PA | | | 3-0 | 25-53-17 | D02462 | | A2 | | | | | | | 150-199, 275-299 |
| 099 | 22 | PA | | | 3-0 | 25-53-17 | D02464 | | B2 | | | | | | | 050-099 |
| 099 | 22 | PA | | | 3-0 | 25-53-17 | D02464 | | B2 | | | | | | | 150-199, 275-299 |
| 100 | 22 | PA | | | 3-0 | 25-53-17 | D02464 | | A2 | | | | | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 32

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | |
| 100 | 22 | | PA | 3-0 | 25-53-17 | D02464 | | A2 | | TB0112Z | 2 | BJ | | 150-199, 275-299 | |
| 101 | 22 | | PA | 5-0 | 25-53-15 | D05218J | | 1 | | D02458 | A3 | | | 050-099 | |
| 101 | 22 | | PA | 4-0 | 25-53-15 | D05218J | | 1 | | D02458 | A3 | | | 150-199, 275-299 | |
| 102 | 22 | | PA | 4-0 | 25-53-15 | D05218J | | 2 | | D02458 | A1 | | | ALL | |
| 103 | 22 | | PA | 5-0 | 25-53-15 | D05218J | | 3 | | D02458 | B3 | | | 050-099 | |
| 103 | 22 | | PA | 4-0 | 25-53-15 | D05218J | | 3 | | D02458 | B3 | | | 150-199, 275-299 | |
| 104 | 22 | | PA | 5-0 | 25-53-15 | D05218J | | 4 | | D02458 | B1 | | | 050-099 | |
| 104 | 22 | | PA | 4-0 | 25-53-15 | D05218J | | 4 | | D02458 | B1 | | | 150-199, 275-299 | |
| 105 | 22 | | PA | 5-0 | 25-53-15 | D05218J | | 5 | | D02458 | C3 | | | 050-099 | |
| 105 | 22 | | PA | 4-0 | 25-53-15 | D05218J | | 5 | | D02458 | C3 | | | 150-199, 275-299 | |
| 106 | 22 | | PA | 4-0 | 25-53-15 | D05218J | | 6 | | D02458 | C1 | | | ALL | |
| 107 | 22 | | PA | 5-0 | 25-53-15 | D05218J | | 7 | | D02460 | A3 | | | 050-099 | |
| 107 | 22 | | PA | 4-0 | 25-53-15 | D05218J | | 7 | | D02460 | A3 | | | 150-199, 275-299 | |
| 108 | 22 | | PA | 4-0 | 25-53-15 | D05218J | | 8 | | D02460 | A1 | | | ALL | |
| 109 | 22 | | PA | 5-0 | 25-53-15 | D02460 | | B3 | | D05218J | 9 | | | 050-099 | |
| 109 | 22 | | PA | 4-0 | 25-53-15 | D02460 | | B3 | | D05218J | 9 | | | 150-199, 275-299 | |
| 110 | 22 | | PA | 4-0 | 25-53-15 | D05218J | | 10 | | D02460 | B1 | | | ALL | |
| 111 | 22 | | PA | 5-0 | 25-53-15 | D05218J | | 11 | | D02460 | C3 | | | 050-099 | |
| 111 | 22 | | PA | 4-0 | 25-53-15 | D05218J | | 11 | | D02460 | C3 | | | 150-199, 275-299 | |
| 112 | 22 | | PA | 4-0 | 25-53-15 | D05218J | | 12 | | D02460 | C1 | | | ALL | |
| 113 | 22 | | PA | 5-0 | 25-53-16 | D05218J | | 13 | | D02454 | A3 | | | 050-099 | |
| 113 | 22 | | PA | 4-0 | 25-53-16 | D05218J | | 13 | | D02454 | A3 | | | 150-199, 275-299 | |
| 114 | 22 | | PA | 4-0 | 25-53-16 | D05218J | | 14 | | TB0112Y | C013 | BJ | | 050-099 | |
| 114 | 22 | | PA | 4-0 | 25-53-16 | D05218J | | 14 | | TB0112G | 13 | 2 | | 150-199, 275-299 | |
| 115 | 22 | | PA | 5-0 | 25-53-16 | D05218J | | 15 | | D02454 | B3 | | | 050-099 | |
| 115 | 22 | | PA | 4-0 | 25-53-16 | D05218J | | 15 | | D02454 | B3 | | | 150-199, 275-299 | |
| 116 | 22 | | PA | 4-0 | 25-53-16 | D05218J | | 16 | | TB0112G | 14 | 2 | | ALL | |
| 117 | 22 | | PA | 5-0 | 25-53-16 | D05218J | | 17 | | D02454 | C1 | | | 050-099 | |
| 117 | 22 | | PA | 4-0 | 25-53-16 | D05218J | | 17 | | D02454 | C1 | | | 150-199, 275-299 | |
| 118 | 22 | | PA | 5-0 | 25-53-16 | D05218J | | 18 | | D02454 | C3 | | | 050-099 | |
| 118 | 22 | | PA | 4-0 | 25-53-16 | D05218J | | 18 | | D02454 | C3 | | | 150-199, 275-299 | |
| 119 | 22 | | PA | 5-0 | 25-53-16 | D05218J | | 19 | | D02454 | D1 | | | 050-099 | |
| 119 | 22 | | PA | 4-0 | 25-53-16 | D05218J | | 19 | | D02454 | D1 | | | 150-199, 275-299 | |
| 120 | 22 | | PA | 5-0 | 25-53-16 | D05218J | | 20 | | D02454 | D3 | | | 050-099 | |
| 120 | 22 | | PA | 4-0 | 25-53-16 | D05218J | | 20 | | D02454 | D3 | | | 150-199, 275-299 | |
| 121 | 22 | | PA | 4-0 | 25-53-17 | D05218J | | 21 | | D02464 | B1 | | | 050-099 | |
| 121 | 22 | | PA | 4-0 | 25-53-17 | D02464 | | B1 | | D05218J | 21 | | | 150-199, 275-299 | |
| 122 | 22 | | PA | 4-0 | 25-53-17 | D05218J | | 22 | | D02464 | B3 | | | 050-099 | |
| 122 | 22 | | PA | 4-0 | 25-53-17 | D02464 | | B3 | | D05218J | 22 | | | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 33

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | |
| 123 | 22 | | PA | 4-0 | 25-53-17 | D02462 | | B3 | | | | D05218J | 23 | | | ALL |
| 124 | 22 | | PA | 4-0 | 25-53-17 | D05218J | | 24 | | | | D02464 | A1 | | | 050-099 |
| 124 | 22 | | PA | 4-0 | 25-53-17 | D02464 | | A1 | | | | D05218J | 24 | | | 150-199, 275-299 |
| 125 | 22 | | PA | 4-0 | 25-53-17 | D05218J | | 25 | | | | D02464 | A3 | | | 050-099 |
| 125 | 22 | | PA | 4-0 | 25-53-17 | D02464 | | A3 | | | | D05218J | 25 | | | 150-199, 275-299 |
| 126 | 22 | | PA | 4-0 | 25-53-17 | D02462 | | A3 | | | | D05218J | 26 | | | ALL |
| 130 | 22 | | PA | 2-0 | 25-53-16 | D02456 | | A3 | | | | D02454 | A2 | | | 050-099 |
| 130 | 22 | | PA | 1-0 | 25-53-16 | D02456 | | A3 | | | | D02454 | A2 | | | 150-199, 275-299 |
| 131 | 22 | | PA | 2-0 | 25-53-16 | D02456 | | A1 | | | | TB0112Y | C013 | BJ | | 050-099 |
| 131 | 22 | | PA | 4-0 | 25-53-16 | D02456 | | A1 | | | | TB0112G | 13 | 2 | | 150-199, 275-299 |
| 132 | 22 | | PA | 2-0 | 25-53-16 | D02454 | | A1 | | | | TB0112Y | C013 | BJ | | 050-099 |
| 132 | 22 | | PA | 4-0 | 25-53-16 | D02454 | | A1 | | | | TB0112G | 13 | 2 | | 150-199, 275-299 |
| 133 | 22 | | PA | 2-0 | 25-53-16 | D02456 | | B3 | | | | D02454 | B2 | | | 050-099 |
| 133 | 22 | | PA | 1-0 | 25-53-16 | D02456 | | B3 | | | | D02454 | B2 | | | 150-199, 275-299 |
| 134 | 22 | | PA | 3-0 | 25-53-16 | D02456 | | B1 | | | | TB0112G | 14 | 2 | | 050-099 |
| 134 | 22 | | PA | 4-0 | 25-53-16 | D02456 | | B1 | | | | TB0112G | 14 | 2 | | 150-199, 275-299 |
| 135 | 22 | | PA | 3-0 | 25-53-16 | D02454 | | B1 | | | | TB0112G | 14 | 2 | | 050-099 |
| 135 | 22 | | PA | 4-0 | 25-53-16 | D02454 | | B1 | | | | TB0112G | 14 | 2 | | 150-199, 275-299 |
| 141 | 20 | | PA | 5-0 | 52-34-11 | TB0110G | | 45 | 2 | | | D05614J | 11 | | | 050-099 |
| 141 | 20 | | PA | 4-0 | 52-34-11 | TB0110G | | 45 | 2 | | | D05614J | 11 | | | 150-199, 275-299 |
| 142 | 20 | | PA | 5-0 | 52-34-11 | TB0110G | | 46 | 2 | | | D05614J | 12 | | | 050-099 |
| 142 | 20 | | PA | 4-0 | 52-34-11 | TB0110G | | 46 | 2 | | | D05614J | 12 | | | 150-199, 275-299 |
| 143 | 20 | | PA | 5-0 | 52-34-11 | TB0110G | | 47 | 2 | | | D05614J | 13 | | | 050-099 |
| 143 | 20 | | PA | 4-0 | 52-34-11 | TB0110G | | 47 | 2 | | | D05614J | 13 | | | 150-199, 275-299 |
| 144 | 22 | | PA | 2-0 | 25-53-13 | S00384 | | 5 | C | | | S00384 | 3 | C | | 050-099 |
| 145 | 22 | | PA | 2-0 | 25-53-13 | S00384 | | 7 | C | | | S00384 | 11 | C | | 050-099 |
| 146 | 22 | | PA | 6-0 | 25-53-13 | S00384 | | 11 | C | | | TB0110D | C034 | 2 | | 050-099 |
| 151 | 20 | | PA | 2-0 | 52-34-11 | D02506 | | A2 | | | | TB0110G | 45 | 2 | | 050-099 |
| 151 | 20 | | PA | 1-0 | 52-34-11 | D02506 | | A2 | | | | TB0110G | 45 | 2 | | 150-199, 275-299 |
| 152 | 20 | | PA | 2-0 | 52-34-11 | D02506 | | B2 | | | | TB0110G | 46 | 2 | | 050-099 |
| 152 | 20 | | PA | 1-0 | 52-34-11 | D02506 | | B2 | | | | TB0110G | 46 | 2 | | 150-199, 275-299 |
| 153 | 20 | | PA | 2-0 | 52-34-11 | D02506 | | C2 | | | | TB0110G | 47 | 2 | | 050-099 |
| 153 | 20 | | PA | 1-0 | 52-34-11 | D02506 | | C2 | | | | TB0110G | 47 | 2 | | 150-199, 275-299 |
| 154 | 20 | | PA | 2-0 | 52-34-11 | D02506 | | A1 | | | | D02508 | A3 | | | 050-099 |
| 154 | 20 | | PA | 1-0 | 52-34-11 | D02506 | | A1 | | | | D02508 | A3 | | | 150-199, 275-299 |
| 155 | 20 | | PA | 2-0 | 52-34-11 | D02506 | | B1 | | | | D02508 | B3 | | | 050-099 |
| 155 | 20 | | PA | 1-0 | 52-34-11 | D02506 | | B1 | | | | D02508 | B3 | | | 150-199, 275-299 |
| 156 | 20 | | PA | 2-0 | 52-34-11 | D02506 | | C1 | | | | D02508 | C3 | | | 050-099 |
| 156 | 20 | | PA | 1-0 | 52-34-11 | D02506 | | C1 | | | | D02508 | C3 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 34

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 157 | 20 | | PA | 2-0 | 52-34-11 | D02506 | | A3 | | | | D02508 | | A1 | | | 050-099 |
| 157 | 20 | | PA | 1-0 | 52-34-11 | D02506 | | A3 | | | | D02508 | | A1 | | | 150-199, 275-299 |
| 158 | 20 | | PA | 2-0 | 52-34-11 | D02506 | | B3 | | | | D02508 | | C1 | | | 050-099 |
| 158 | 20 | | PA | 1-0 | 52-34-11 | D02506 | | B3 | | | | D02508 | | C1 | | | 150-199, 275-299 |
| 159 | 20 | | PA | 2-0 | 52-34-11 | D02506 | | C3 | | | | D02508 | | B1 | | | 050-099 |
| 159 | 20 | | PA | 1-0 | 52-34-11 | D02506 | | C3 | | | | D02508 | | B1 | | | 150-199, 275-299 |
| 161 | 20 | | PA | 2-0 | 52-34-11 | D02502 | | A2 | | | | TB0110G | 45 | 2 | | | 050-099 |
| 161 | 20 | | PA | 1-0 | 52-34-11 | D02502 | | A2 | | | | TB0110G | 45 | 2 | | | 150-199, 275-299 |
| 162 | 20 | | PA | 2-0 | 52-34-11 | D02502 | | B2 | | | | TB0110G | 46 | 2 | | | 050-099 |
| 162 | 20 | | PA | 1-0 | 52-34-11 | D02502 | | B2 | | | | TB0110G | 46 | 2 | | | 150-199, 275-299 |
| 163 | 20 | | PA | 2-0 | 52-34-11 | D02502 | | C2 | | | | TB0110G | 47 | 2 | | | 050-099 |
| 163 | 20 | | PA | 1-0 | 52-34-11 | D02502 | | C2 | | | | TB0110G | 47 | 2 | | | 150-199, 275-299 |
| 164 | 20 | | PA | 2-0 | 52-34-11 | D02502 | | A1 | | | | D02504 | | A3 | | | 050-099 |
| 164 | 20 | | PA | 1-0 | 52-34-11 | D02502 | | A1 | | | | D02504 | | A3 | | | 150-199, 275-299 |
| 165 | 20 | | PA | 2-0 | 52-34-11 | D02502 | | B1 | | | | D02504 | | B3 | | | 050-099 |
| 165 | 20 | | PA | 1-0 | 52-34-11 | D02502 | | B1 | | | | D02504 | | B3 | | | 150-199, 275-299 |
| 166 | 20 | | PA | 2-0 | 52-34-11 | D02502 | | C1 | | | | D02504 | | C3 | | | 050-099 |
| 166 | 20 | | PA | 1-0 | 52-34-11 | D02502 | | C1 | | | | D02504 | | C3 | | | 150-199, 275-299 |
| 167 | 20 | | PA | 2-0 | 52-34-11 | D02502 | | A3 | | | | D02504 | | A1 | | | 050-099 |
| 167 | 20 | | PA | 1-0 | 52-34-11 | D02502 | | A3 | | | | D02504 | | A1 | | | 150-199, 275-299 |
| 168 | 20 | | PA | 2-0 | 52-34-11 | D02502 | | B3 | | | | D02504 | | C1 | | | 050-099 |
| 168 | 20 | | PA | 1-0 | 52-34-11 | D02502 | | B3 | | | | D02504 | | C1 | | | 150-199, 275-299 |
| 169 | 20 | | PA | 2-0 | 52-34-11 | D02502 | | C3 | | | | D02504 | | B1 | | | 050-099 |
| 169 | 20 | | PA | 1-0 | 52-34-11 | D02502 | | C3 | | | | D02504 | | B1 | | | 150-199, 275-299 |
| 170 | 08 | | PA | 5-0 | 25-53-11 | C00015 | | | 2 | D | | K00245 | | A1 | E | | 050-099 |
| 171 | 20 | | PA | 4-0 | 52-34-11 | D02508 | | A2 | | | | D04304J | | 11 | | | 050-099 |
| 171 | 20 | | PA | 3-0 | 52-34-11 | D02508 | | A2 | | | | D04304J | | 11 | | | 150-199, 275-299 |
| 172 | 20 | | PA | 4-0 | 52-34-11 | D02508 | | B2 | | | | D04304J | | 12 | | | 050-099 |
| 172 | 20 | | PA | 3-0 | 52-34-11 | D02508 | | B2 | | | | D04304J | | 12 | | | 150-199, 275-299 |
| 173 | 20 | | PA | 4-0 | 52-34-11 | D02508 | | C2 | | | | D04304J | | 13 | | | 050-099 |
| 173 | 20 | | PA | 3-0 | 52-34-11 | D02508 | | C2 | | | | D04304J | | 13 | | | 150-199, 275-299 |
| 174 | 20 | | PA | 4-0 | 52-34-11 | D02504 | | A2 | | | | D04304J | | 14 | | | 050-099 |
| 174 | 20 | | PA | 3-0 | 52-34-11 | D02504 | | A2 | | | | D04304J | | 14 | | | 150-199, 275-299 |
| 175 | 20 | | PA | 4-0 | 52-34-11 | D02504 | | B2 | | | | D04304J | | 24 | | | 050-099 |
| 175 | 20 | | PA | 3-0 | 52-34-11 | D02504 | | B2 | | | | D04304J | | 24 | | | 150-199, 275-299 |
| 176 | 20 | | PA | 4-0 | 52-34-11 | D02504 | | C2 | | | | D04304J | | 16 | | | 050-099 |
| 176 | 20 | | PA | 3-0 | 52-34-11 | D02504 | | C2 | | | | D04304J | | 16 | | | 150-199, 275-299 |
| 177 | 22 | | PA | 5-0 | 25-53-13 | S00678 | | | 5 | B | * | TB0110Z | | 39 | BJ | | 150-199, 275-299 |
| 178 | 22 | | PA | 4-0 | 25-53-14 | TB0110Z | | | 43 | BJ | | D05614J | | 15 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 35

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|------|----|--|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | | | |
| 179 | 20 | | PA | | 4-0 | 26-16-21 | D05214J | | 7 | | | | | | TB0112G | 17 | 2 | | ALL |
| 180 | 20 | | PA | | 4-0 | 26-16-21 | D02520 | | 11 | | | | | | TB0112G | 17 | 2 | | ALL |
| 181 | 20 | | PA | | 5-0 | 26-16-21 | C00060 | | 2 | D | | | | | D05214J | 1 | | | 050-099 |
| 181 | 20 | | PA | | 4-0 | 26-16-21 | C00060 | | 2 | D | | | | | D05214J | 1 | | | 150-199, 275-299 |
| 182 | 20 | | PA | | 5-0 | 26-16-21 | C00061 | | 2 | D | | | | | D05214J | 2 | | | 050-099 |
| 182 | 20 | | PA | | 4-0 | 26-16-21 | C00061 | | 2 | D | | | | | D05214J | 2 | | | 150-199, 275-299 |
| 183 | 20 | | PA | | 8-0 | 26-16-21 | C00060 | | 1 | D | | | | | D02520 | 9 | | | 050-099 |
| 183 | 20 | | PA | | 6-0 | 26-16-21 | C00060 | | 1 | D | | | | | D02520 | 9 | | | 150-199, 275-299 |
| 184 | 20 | | PA | | 8-0 | 26-16-21 | C00061 | | 1 | D | | | | | D02520 | 10 | | | 050-099 |
| 184 | 20 | | PA | | 6-0 | 26-16-21 | C00061 | | 1 | D | | | | | D02520 | 10 | | | 150-199, 275-299 |
| 189 | 22 | | PA | | 4-0 | 25-53-14 | D01288 | | A2 | | | | | | TB0112Z | 26 | BJ | | 150-199, 275-299 |
| 190 | 20 | | PA | | 2-0 | 26-16-21 | D02522 | | 11 | | | | | | TB0112G | 17 | 2 | | 050-099 |
| 190 | 20 | | PA | | 4-0 | 26-16-21 | D02522 | | 11 | | | | | | TB0112G | 17 | 2 | | 150-199, 275-299 |
| 191 | 20 | | PA | | 5-0 | 26-16-21 | C00062 | | 2 | D | | | | | D05214J | 11 | | | 050-099 |
| 191 | 20 | | PA | | 4-0 | 26-16-21 | C00062 | | 2 | D | | | | | D05214J | 11 | | | 150-199, 275-299 |
| 192 | 20 | | PA | | 5-0 | 26-16-21 | C00063 | | 2 | D | | | | | D05214J | 12 | | | 050-099 |
| 192 | 20 | | PA | | 4-0 | 26-16-21 | C00063 | | 2 | D | | | | | D05214J | 12 | | | 150-199, 275-299 |
| 193 | 20 | | PA | | 7-0 | 26-16-21 | C00062 | | 1 | D | | | | | D02522 | 9 | | | 050-099 |
| 193 | 20 | | PA | | 6-0 | 26-16-21 | C00062 | | 1 | D | | | | | D02522 | 9 | | | 150-199, 275-299 |
| 194 | 20 | | PA | | 7-0 | 26-16-21 | C00063 | | 1 | D | | | | | D02522 | 10 | | | 050-099 |
| 194 | 20 | | PA | | 6-0 | 26-16-21 | C00063 | | 1 | D | | | | | D02522 | 10 | | | 150-199, 275-299 |
| 195 | 22 | | PA | | 7-0 | 25-53-15 | C00076 | | 1 | D | * | | | | TB0306Z | 12 | BJ | | 050-099 |
| 195 | 22 | | PA | | 5-0 | 25-53-15 | C00076 | | 1 | D | * | | | | TB0306Z | 12 | BJ | | 150-199, 275-299 |
| 196 | 22 | | PA | | 7-0 | 25-53-14 | D11630 | | 4 | | | | | | TB0306Y | C005 | BJ | | 050-099 |
| 196 | 22 | | PA | | 4-0 | 25-53-14 | D11630 | | 4 | | | | | | TB0110Z | 33 | BJ | | 150-199, 275-299 |
| 197 | 22 | | PA | | 7-0 | 25-53-14 | D11630 | | 5 | | | | | | TB0306Y | C004 | BJ | | 050-099 |
| 197 | 22 | | PA | | 4-0 | 25-53-14 | D02490 | | 1 | | | | | | D11630 | 5 | | | 150-199, 275-299 |
| 198 | 22 | | PA | | 2-0 | 25-53-14 | D11630 | | 3 | | | | | | TB0110H | 39 | 2 | | 050-099 |
| 198 | 22 | | PA | | 4-0 | 25-53-14 | D02490 | | 6 | | | | | | TB0110Z | 15 | BJ | | 150-199, 275-299 |
| 199 | 22 | | PA | | 5-0 | 25-53-14 | D11630 | | 7 | | | | | | TB0112Z | 27 | BJ | | 050-099 |
| 199 | 22 | | PA | | 4-0 | 25-53-14 | D11630 | | 7 | | | | | | TB0112Z | 6 | BJ | | 150-199, 275-299 |
| 201B | 24 | | PL | A | 2-0 | 52-71-13 | D08070J | | 1 | | | | | | D04304J | 1 | | | ALL |
| 201R | 24 | | PL | A | 0-0 | 52-71-13 | D08070J | | 2 | | | | | | D04304J | 2 | | | ALL |
| 202B | 24 | | PL | B | 2-0 | 52-34-13 | D08070J | | 3 | | | | | | D04304J | 3 | | | ALL |
| 202R | 24 | | PL | B | 0-0 | 52-34-13 | D08070J | | 4 | | | | | | D04304J | 4 | | | ALL |
| 203B | 24 | | PL | C | 2-0 | 52-34-13 | D08070J | | 5 | | | | | | D04304J | 5 | | | ALL |
| 203R | 24 | | PL | C | 0-0 | 52-34-13 | D08070J | | 6 | | | | | | D04304J | 6 | | | ALL |
| 204B | 24 | | PL | D | 2-0 | 52-71-13 | D08070J | | 7 | | | | | | D04304J | 7 | | | ALL |
| 204R | 24 | | PL | D | 0-0 | 52-71-13 | D08070J | | 8 | | | | | | D04304J | 8 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 36

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | |
| 205B | 24 | PL | E | 2-0 | 52-34-13 | D08070J | | 9 | | | | D04304J | 9 | | ALL | |
| 205R | 24 | PL | E | 0-0 | 52-34-13 | D08070J | | 10 | | | | D04304J | 10 | | ALL | |
| 255 | 22 | PA | | 7-0 | 25-53-11 | TB0112Z | | 5 | BJ | | | S00563 | 5 | C | 150-199, 275-299 | |
| 285 | 22 | PA | | 4-0 | 25-53-17 | D01608 | | B3 | | | | D05218J | 29 | | 150-199, 275-299 | |
| 301B | 20 | PC | AA | 7-0 | 25-53-12 | C00085 | | A2 | D | | | D05220J | 1 | | 050-099 | |
| 301B | 20 | PC | AA | 5-0 | 25-53-12 | C00170 | | A2 | D | | | D05220J | 1 | | 150-199, 275-299 | |
| 301R | 20 | PC | AA | 0-0 | 25-53-12 | C00085 | | B2 | D | | | D05220J | 2 | | 050-099 | |
| 301R | 20 | PC | AA | 0-0 | 25-53-12 | C00170 | | B2 | D | | | D05220J | 2 | | 150-199, 275-299 | |
| 301Y | 20 | PC | AA | 0-0 | 25-53-12 | C00085 | | C2 | D | | | D05220J | 3 | | 050-099 | |
| 301Y | 20 | PC | AA | 0-0 | 25-53-12 | C00170 | | C2 | D | | | D05220J | 3 | | 150-199, 275-299 | |
| 302B | 20 | PC | AB | 7-0 | 25-53-12 | C00086 | | A2 | D | | | D05220J | 4 | | 050-099 | |
| 302B | 20 | PC | AB | 5-0 | 25-53-12 | C00171 | | A2 | D | | | D05220J | 4 | | 150-199, 275-299 | |
| 302R | 20 | PC | AB | 0-0 | 25-53-12 | C00086 | | B2 | D | | | D05220J | 5 | | 050-099 | |
| 302R | 20 | PC | AB | 0-0 | 25-53-12 | C00171 | | B2 | D | | | D05220J | 5 | | 150-199, 275-299 | |
| 302Y | 20 | PC | AB | 0-0 | 25-53-12 | C00086 | | C2 | D | | | D05220J | 6 | | 050-099 | |
| 302Y | 20 | PC | AB | 0-0 | 25-53-12 | C00171 | | C2 | D | | | D05220J | 6 | | 150-199, 275-299 | |
| 303B | 20 | PC | AC | 6-0 | 25-53-12 | C00087 | | A2 | D | | | D05220J | 7 | | 050-099 | |
| 303B | 20 | PC | AC | 4-0 | 25-53-12 | C00173 | | A2 | D | | | D05220J | 7 | | 150-199, 275-299 | |
| 303R | 20 | PC | AC | 0-0 | 25-53-12 | C00087 | | B2 | D | | | D05220J | 8 | | 050-099 | |
| 303R | 20 | PC | AC | 0-0 | 25-53-12 | C00173 | | B2 | D | | | D05220J | 8 | | 150-199, 275-299 | |
| 303Y | 20 | PC | AC | 0-0 | 25-53-12 | C00087 | | C2 | D | | | D05220J | 9 | | 050-099 | |
| 303Y | 20 | PC | AC | 0-0 | 25-53-12 | C00173 | | C2 | D | | | D05220J | 9 | | 150-199, 275-299 | |
| 304B | 20 | PC | AD | 6-0 | 25-53-12 | C00088 | | A2 | D | | | D05220J | 11 | | 050-099 | |
| 304B | 20 | PC | AD | 5-0 | 25-53-12 | C00172 | | A2 | D | | | D05220J | 11 | | 150-199, 275-299 | |
| 304R | 20 | PC | AD | 0-0 | 25-53-12 | C00088 | | B2 | D | | | D05220J | 12 | | 050-099 | |
| 304R | 20 | PC | AD | 0-0 | 25-53-12 | C00172 | | B2 | D | | | D05220J | 12 | | 150-199, 275-299 | |
| 304Y | 20 | PC | AD | 0-0 | 25-53-12 | C00088 | | C2 | D | | | D05220J | 13 | | 050-099 | |
| 304Y | 20 | PC | AD | 0-0 | 25-53-12 | C00172 | | C2 | D | | | D05220J | 13 | | 150-199, 275-299 | |
| 305B | 20 | PC | AE | 7-0 | 25-53-12 | C00081 | | A1 | D | | | D05222J | 1 | | 050-099 | |
| 305B | 20 | PC | AE | 5-0 | 25-53-12 | C00166 | | A1 | D | | | D05222J | 1 | | 150-199, 275-299 | |
| 305R | 20 | PC | AE | 0-0 | 25-53-12 | C00081 | | B1 | D | | | D05222J | 2 | | 050-099 | |
| 305R | 20 | PC | AE | 0-0 | 25-53-12 | C00166 | | B1 | D | | | D05222J | 2 | | 150-199, 275-299 | |
| 305Y | 20 | PC | AE | 0-0 | 25-53-12 | C00081 | | C1 | D | | | D05222J | 3 | | 050-099 | |
| 305Y | 20 | PC | AE | 0-0 | 25-53-12 | C00166 | | C1 | D | | | D05222J | 3 | | 150-199, 275-299 | |
| 306B | 20 | PC | AF | 7-0 | 25-53-12 | C00082 | | A1 | D | | | D05222J | 4 | | 050-099 | |
| 306B | 20 | PC | AF | 5-0 | 25-53-12 | C00167 | | A1 | D | | | D05222J | 4 | | 150-199, 275-299 | |
| 306R | 20 | PC | AF | 0-0 | 25-53-12 | C00082 | | B1 | D | | | D05222J | 5 | | 050-099 | |
| 306R | 20 | PC | AF | 0-0 | 25-53-12 | C00167 | | B1 | D | | | D05222J | 5 | | 150-199, 275-299 | |
| 306Y | 20 | PC | AF | 0-0 | 25-53-12 | C00082 | | C1 | D | | | D05222J | 6 | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 37

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|--------|--------|---------|-------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1066 | 286T1066 | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 306Y | 20 | PC | AF | | 0-0 | 25-53-12 | C00167 | C1 | D | | D05222J | 6 | | | 150-199, 275-299 |
| 307B | 20 | PC | AG | | 6-0 | 25-53-12 | C00083 | A1 | D | | D05222J | 7 | | | 050-099 |
| 307B | 20 | PC | AG | | 4-0 | 25-53-12 | C00168 | A1 | D | | D05222J | 7 | | | 150-199, 275-299 |
| 307R | 20 | PC | AG | | 0-0 | 25-53-12 | C00083 | B1 | D | | D05222J | 8 | | | 050-099 |
| 307R | 20 | PC | AG | | 0-0 | 25-53-12 | C00168 | B1 | D | | D05222J | 8 | | | 150-199, 275-299 |
| 307Y | 20 | PC | AG | | 0-0 | 25-53-12 | C00083 | C1 | D | | D05222J | 9 | | | 050-099 |
| 307Y | 20 | PC | AG | | 0-0 | 25-53-12 | C00168 | C1 | D | | D05222J | 9 | | | 150-199, 275-299 |
| 308B | 20 | PC | AH | | 6-0 | 25-53-12 | C00084 | A1 | D | | D05222J | 11 | | | 050-099 |
| 308B | 20 | PC | AH | | 4-0 | 25-53-12 | C00169 | A1 | D | | D05222J | 11 | | | 150-199, 275-299 |
| 308R | 20 | PC | AH | | 0-0 | 25-53-12 | C00084 | B1 | D | | D05222J | 12 | | | 050-099 |
| 308R | 20 | PC | AH | | 0-0 | 25-53-12 | C00169 | B1 | D | | D05222J | 12 | | | 150-199, 275-299 |
| 308Y | 20 | PC | AH | | 0-0 | 25-53-12 | C00084 | C1 | D | | D05222J | 13 | | | 050-099 |
| 308Y | 20 | PC | AH | | 0-0 | 25-53-12 | C00169 | C1 | D | | D05222J | 13 | | | 150-199, 275-299 |
| 310B | 20 | PC | MJ | | 3-0 | 23-41-11 | SM00002 | | S | | D08070J | 14 | | | ALL |
| 310R | 20 | PC | MJ | | 0-0 | 23-41-11 | SM00001 | | S | | D08070J | 13 | | | ALL |
| 310Y | 20 | PC | MJ | | 0-0 | 23-41-11 | SM00003 | | S | | D08070J | 15 | | | ALL |
| 32A | 20 | PA | | | 5-0 | 25-53-11 | C00010 | | 2 D | | TB0112G | 28 | 2 | | 150-199, 275-299 |
| 32C | 22 | PA | | | 6-0 | 25-53-13 | TB0110Z | | 39 BJ | | S00675 | 5 | B | * | 150-199, 275-299 |
| 32D | 22 | PA | | | 2-0 | 25-53-13 | TB0110G | | 8 2 | | TB0110Z | 21 | BJ | | 150-199, 275-299 |
| 32E | 22 | PA | | | 7-0 | 25-53-13 | S00675 | | 1 B | | TB0110G | 8 | 2 | | 150-199, 275-299 |
| 32F | 22 | PA | | | 2-0 | 25-53-13 | L00815 | | =P \$ | * | L00816 | =P \$ | | * | 150-199, 275-299 |
| 32G | 22 | PA | | | 2-0 | 25-53-13 | L00814 | | =P \$ | * | L00816 | =P \$ | | * | 150-199, 275-299 |
| 32H | 22 | PA | | | 1-0 | 25-53-13 | S00677 | | 1 B | * | L00815 | =G \$ | | | 150-199, 275-299 |
| 32J | 22 | PA | | | 6-0 | 25-53-13 | S00677 | | 4 B | * | TB0112Z | 10 | BJ | | 150-199, 275-299 |
| 32K | 22 | PA | | | 2-0 | 25-53-13 | S00677 | | 5 B | | S00678 | 5 | B | * | 150-199, 275-299 |
| 32L | 22 | PA | | | 1-0 | 25-53-13 | S00677 | | 4 B | * | S00678 | 4 | B | * | 150-199, 275-299 |
| 32M | 22 | PA | | | 1-0 | 25-53-13 | S00677 | | 2 B | * | L00816 | =G \$ | | | 150-199, 275-299 |
| 32N | 22 | PA | | | 5-0 | 25-53-13 | S00677 | | 2 B | * | TB0114D | C012 | 2 | | 150-199, 275-299 |
| 32P | 22 | PA | | | 2-0 | 25-53-13 | L00817 | | =P \$ | * | L00818 | =P \$ | | | 150-199, 275-299 |
| 32R | 22 | PA | | | 1-0 | 25-53-13 | S00679 | | 2 B | * | L00818 | =G \$ | | | 150-199, 275-299 |
| 32T | 22 | PA | | | 2-0 | 25-53-13 | S00679 | | 4 B | | S00678 | 4 | B | * | 150-199, 275-299 |
| 32W | 22 | PA | | | 1-0 | 25-53-13 | S00678 | | 2 B | * | L00817 | =G \$ | | | 150-199, 275-299 |
| 32X | 22 | PA | | | 1-0 | 25-53-13 | S00678 | | 5 B | * | S00679 | 5 | B | | 150-199, 275-299 |
| 33A | 22 | PA | | | 3-0 | 25-53-13 | L00817 | | =P \$ | * | L00815 | =P \$ | | * | 150-199, 275-299 |
| 33B | 22 | PA | | | 1-0 | 25-53-13 | S00678 | | 2 B | * | S00679 | 1 | B | | 150-199, 275-299 |
| 33C | 22 | PA | | | 1-0 | 25-53-13 | S00678 | | 1 B | | S00677 | 2 | B | * | 150-199, 275-299 |
| 33D | 22 | PA | | | 7-0 | 25-53-13 | TB0112D | | C003 2 | | TB0114D | C015 | 2 | | 150-199, 275-299 |
| 33E | 22 | PA | | | 6-0 | 25-53-13 | S00678 | | 2 B | * | TB0110G | 9 | 2 | | 150-199, 275-299 |
| 33F | 22 | PA | | | 3-0 | 25-53-13 | D11682 | | 7 | | TB0110Z | 36 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 38

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 33G | 22 | | PA | 4-0 | 25-53-13 | D11682 | | 3 | | | | | TB0114D | A014 | 2 | | 150-199, 275-299 |
| 33H | 22 | | PA | 3-0 | 25-53-13 | D11680 | | 7 | | | | | TB0110Z | 35 | BJ | | 150-199, 275-299 |
| 33J | 22 | | PA | 4-0 | 25-53-13 | D11680 | | 3 | | | | | TB0114D | A013 | 2 | | 150-199, 275-299 |
| 33K | 22 | | PA | 3-0 | 25-53-13 | D11666 | | 7 | | | | | TB0110Z | 36 | BJ | | 150-199, 275-299 |
| 33L | 22 | | PA | 4-0 | 25-53-13 | D11666 | | 3 | | | | | TB0112D | A003 | 2 | | 150-199, 275-299 |
| 33M | 22 | | PA | 3-0 | 25-53-13 | D11684 | | 7 | | | | | TB0110Z | 35 | BJ | | 150-199, 275-299 |
| 33N | 22 | | PA | 4-0 | 25-53-13 | D11684 | | 3 | | | | | TB0114D | A015 | 2 | | 150-199, 275-299 |
| 33P | 22 | | PA | 2-0 | 25-53-13 | D11146 | | 3 | | | | | TB0110G | 9 | 2 | | 150-199, 275-299 |
| 33R | 22 | | PA | 5-0 | 25-53-13 | D11148 | | 3 | | | | | TB0114D | C015 | 2 | | 150-199, 275-299 |
| 33S | 22 | | PA | 5-0 | 25-53-13 | TB0114D | | | C014 | 2 | | | TB0110G | 9 | 2 | | 150-199, 275-299 |
| 33T | 22 | | PA | 5-0 | 25-53-13 | TB0114D | | | C013 | 2 | | | TB0110G | 9 | 2 | | 150-199, 275-299 |
| 33W | 22 | | PA | 4-0 | 25-53-14 | D01684 | | | B2 | | | | TB0112Z | 10 | BJ | | 150-199, 275-299 |
| 33X | 22 | | PA | 4-0 | 25-53-14 | D01684 | | | A1 | | | | TB0110Z | 19 | BJ | | 150-199, 275-299 |
| 34A | 22 | | PA | 5-0 | 25-53-14 | C00010 | | 1 | | D | | | TB0112Z | 10 | BJ | | 150-199, 275-299 |
| 34B | 22 | | PA | 2-0 | 25-53-14 | D11150 | | 3 | | | | | TB0110Z | 41 | BJ | | 150-199, 275-299 |
| 34C | 22 | | PA | 4-0 | 25-53-14 | D01686 | | | B2 | | | | TB0112Z | 10 | BJ | | 150-199, 275-299 |
| 34D | 22 | | PA | 4-0 | 25-53-14 | D01686 | | | A1 | | | | TB0110Z | 6 | BJ | | 150-199, 275-299 |
| 34E | 22 | | PA | 2-0 | 25-53-14 | TB0110Z | | 7 | | BJ | | | TB0110Z | 18 | BJ | | 150-199, 275-299 |
| 34F | 22 | | PA | 4-0 | 25-53-14 | D11150 | | 2 | | | | | TB0112Z | 25 | BJ | | 150-199, 275-299 |
| 34G | 22 | | PA | 4-0 | 25-53-14 | D11150 | | 6 | | | | | TB0112Z | 26 | BJ | | 150-199, 275-299 |
| 34H | 22 | | PA | 4-0 | 25-53-14 | D11150 | | 7 | | | | | TB0112Z | 34 | BJ | | 150-199, 275-299 |
| 34J | 22 | | PA | 1-0 | 25-53-14 | D11704 | | 6 | | | | | D02484 | 8 | | | 150-199, 275-299 |
| 34K | 22 | | PA | 2-0 | 25-53-14 | D02484 | | 6 | | | | | TB0110Z | 43 | BJ | | 150-199, 275-299 |
| 34L | 22 | | PA | 4-0 | 25-53-14 | D02488 | | 5 | | | | | TB0112Y | C011 | BJ | | 150-199, 275-299 |
| 34M | 22 | | PA | 4-0 | 25-53-14 | D13050 | | 6 | | | | | TB0112Y | C011 | BJ | | 150-199, 275-299 |
| 34N | 22 | | PA | 4-0 | 25-53-14 | D11682 | | 6 | | | | | TB0110Z | 7 | BJ | | 150-199, 275-299 |
| 34P | 22 | | PA | 4-0 | 25-53-14 | D11682 | | 2 | | | | | TB0112Z | 6 | BJ | | 150-199, 275-299 |
| 34R | 22 | | PA | 4-0 | 25-53-14 | D11684 | | 6 | | | | | TB0110Z | 7 | BJ | | 150-199, 275-299 |
| 34S | 22 | | PA | 2-0 | 25-53-14 | D11146 | | 2 | | | | | TB0110Z | 19 | BJ | | 150-199, 275-299 |
| 34T | 22 | | PA | 2-0 | 25-53-14 | D11146 | | 7 | | | | | TB0110Z | 33 | BJ | | 150-199, 275-299 |
| 34W | 22 | | PA | 2-0 | 25-53-14 | D11148 | | 2 | | | | | TB0110Z | 19 | BJ | | 150-199, 275-299 |
| 34X | 22 | | PA | 3-0 | 25-53-14 | D11146 | | 5 | | | | | TB0112Z | 6 | BJ | | 150-199, 275-299 |
| 35A | 22 | | PA | 2-0 | 25-53-14 | D11148 | | 7 | | | | | TB0110Z | 33 | BJ | | 150-199, 275-299 |
| 35B | 22 | | PA | 4-0 | 25-53-14 | D11680 | | 2 | | | | | TB0112Z | 6 | BJ | | 150-199, 275-299 |
| 35C | 22 | | PA | 4-0 | 25-53-14 | D11666 | | 6 | | | | | TB0110Z | 7 | BJ | | 150-199, 275-299 |
| 35D | 22 | | PA | 4-0 | 25-53-14 | D11666 | | 2 | | | | | TB0112Y | A012 | BJ | | 150-199, 275-299 |
| 35E | 22 | | PA | 4-0 | 25-53-14 | D11684 | | 2 | | | | | TB0112Y | A012 | BJ | | 150-199, 275-299 |
| 35F | 22 | | PA | 4-0 | 25-53-14 | D11680 | | 6 | | | | | TB0110Z | 7 | BJ | | 150-199, 275-299 |
| 35G | 22 | | PA | 4-0 | 25-53-14 | D11682 | | 1 | | | | | D05224J | 3 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 39

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | | |
| 35H | 22 | | PA | 4-0 | 25-53-14 | D11682 | | 5 | | | | | D05224J | | 6 | | | 150-199, 275-299 |
| 35J | 22 | | PA | 4-0 | 25-53-14 | D11680 | | 1 | | | | | D05224J | | 9 | | | 150-199, 275-299 |
| 35K | 22 | | PA | 4-0 | 25-53-14 | D11680 | | 5 | | | | | D05224J | | 13 | | | 150-199, 275-299 |
| 35L | 22 | | PA | 4-0 | 25-53-14 | D11666 | | 1 | | | | | D05224J | | 16 | | | 150-199, 275-299 |
| 35N | 22 | | PA | 4-0 | 25-53-14 | D11684 | | 5 | | | | | D05224J | | 29 | | | 150-199, 275-299 |
| 35P | 22 | | PA | 4-0 | 25-53-14 | D11684 | | 1 | | | | | D05224J | | 33 | | | 150-199, 275-299 |
| 35R | 22 | | PA | 4-0 | 25-53-14 | D11148 | | 5 | | | | | TB0112Y | A012 | | BJ | | 150-199, 275-299 |
| 35S | 22 | | PA | 4-0 | 25-53-15 | D02444 | | 7 | | | | | TB0112Z | 34 | | BJ | | 150-199, 275-299 |
| 35T | 22 | | PA | 5-0 | 25-53-14 | D05224J | | 19 | | | | | TB0306Y | C005 | | BJ | | 050-099 |
| 35T | 22 | | PA | 4-0 | 25-53-14 | D11666 | | 5 | | | | | D05224J | 19 | | | | 150-199, 275-299 |
| 35W | 22 | | PA | 6-0 | 25-53-13 | S00679 | | 2 | B | * | | | TB0112D | C003 | 2 | | | 150-199, 275-299 |
| 35X | 22 | | PA | 4-0 | 25-53-14 | D05216J | | 15 | | | | | TB0112Z | 25 | | BJ | | 150-199, 275-299 |
| 35Y | 22 | | PA | 4-0 | 25-53-14 | D05216J | | 14 | | | | | TB0112Z | 26 | | BJ | | 150-199, 275-299 |
| 37A | 22 | | PA | 7-0 | 25-53-15 | D02458 | | D3 | | | | | TB0306Y | A001 | | BJ | | 050-099 |
| 37A | 22 | | PA | 6-0 | 25-53-15 | D02458 | | D3 | | | | | TB0306Y | A001 | | BJ | | 150-199, 275-299 |
| 37B | 22 | | PA | 5-0 | 25-53-15 | D02458 | | D2 | | | | | TB0114H | 3 | 2 | | | 050-099 |
| 37B | 22 | | PA | 4-0 | 25-53-15 | D02458 | | D2 | | | | | TB0112Z | 5 | | BJ | | 150-199, 275-299 |
| 37C | 22 | | PA | 7-0 | 25-53-15 | D02458 | | D1 | | | | | TB0306Y | A002 | | BJ | | 050-099 |
| 37C | 22 | | PA | 6-0 | 25-53-15 | D02458 | | D1 | | | | | TB0306Y | A002 | | BJ | | 150-199, 275-299 |
| 37D | 22 | | PA | 7-0 | 25-53-15 | D02460 | | D3 | | | | | TB0306Y | A003 | | BJ | | 050-099 |
| 37D | 22 | | PA | 6-0 | 25-53-15 | D02460 | | D3 | | | | | TB0306Y | A003 | | BJ | | 150-199, 275-299 |
| 37E | 22 | | PA | 5-0 | 25-53-15 | D02460 | | D2 | | | | | TB0114H | 3 | 2 | | | 050-099 |
| 37E | 22 | | PA | 4-0 | 25-53-15 | D02460 | | D2 | | | | | TB0112Z | 5 | | BJ | | 150-199, 275-299 |
| 37F | 22 | | PA | 7-0 | 25-53-15 | D02460 | | D1 | | | | | TB0306Y | A004 | | BJ | | 050-099 |
| 37F | 22 | | PA | 6-0 | 25-53-15 | D02460 | | D1 | | | | | TB0306Y | A004 | | BJ | | 150-199, 275-299 |
| 37G | 22 | | PA | 4-0 | 25-53-16 | D05216J | | 6 | | | | | TB0112Y | A012 | | BJ | | 050-099 |
| 37G | 22 | | PA | 4-0 | 25-53-16 | D05216J | | 6 | | | | | TB0110Z | 44 | | BJ | | 150-199, 275-299 |
| 37H | 22 | | PA | 4-0 | 25-53-16 | D05216J | | 22 | | | | | D11620 | 6 | | | | ALL |
| 37J | 22 | | PA | 4-0 | 25-53-16 | D05216J | | 5 | | | | | TB0306Z | 13 | | BJ | | ALL |
| 37K | 22 | | PA | 7-0 | 25-53-16 | D02454 | | X1 | | | | | TB0306Y | C001 | | BJ | | 050-099 |
| 37K | 22 | | PA | 6-0 | 25-53-16 | D02454 | | X1 | | | | | TB0306Y | C001 | | BJ | | 150-199, 275-299 |
| 37L | 22 | | PA | 7-0 | 25-53-16 | D02456 | | X1 | | | | | TB0306Z | 13 | | BJ | | ALL |
| 37M | 22 | | PA | 5-0 | 25-53-17 | D05216J | | 24 | | | | | D10610 | 7 | | | | 050-099 |
| 37M | 22 | | PA | 4-0 | 25-53-17 | D05216J | | 24 | | | | | TB0306Y | C004 | | BJ | | 150-199, 275-299 |
| 37N | 22 | | PA | 5-0 | 25-53-17 | D05216J | | 23 | | | | | D10612 | 7 | | | | 050-099 |
| 37N | 22 | | PA | 4-0 | 25-53-17 | D05216J | | 23 | | | | | TB0306Y | C005 | | BJ | | 150-199, 275-299 |
| 37P | 22 | | PA | 6-0 | 25-53-17 | TB0112G | | 32 | 2 | | | | TB0306Y | C006 | | BJ | | ALL |
| 37S | 22 | | PA | 7-0 | 25-53-17 | S00563 | | 6 | | C | | | TB0306Y | A006 | | BJ | | 050-099 |
| 37S | 22 | | PA | 7-0 | 25-53-17 | TB0306Y | | A006 | | BJ | | | S00563 | 6 | | C | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 40

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 37T | 22 | | PA | 4-0 | 25-53-13 | TB0114H | 5 | 2 | | | | | TB0306Z | 8 | BJ | | 050-099 |
| 37T | 22 | | PA | 6-0 | 25-53-13 | TB0110Z | 39 | BJ | | | | | TB0306Z | 8 | BJ | | 150-199, 275-299 |
| 37U | 22 | | PA | 1-0 | 25-53-13 | TB0306Z | 9 | BJ | | | | | TB0306Z | 8 | BJ | | ALL |
| 37V | 22 | | PA | 5-0 | 25-53-16 | TB0306Z | 11 | BJ | | | | | TB0114H | 3 | 2 | | 050-099 |
| 37V | 22 | | PA | 6-0 | 25-53-16 | TB0306Z | 11 | BJ | | | | | TB0112Z | 5 | BJ | | 150-199, 275-299 |
| 38A | 22 | | PA | 7-0 | 25-53-15 | D10600 | A1 | | | | | | TB0112H | 7 | 2 | | 050-099 |
| 38A | 22 | | PA | 7-0 | 25-53-15 | D10600 | A1 | | | | | | TB0112Z | 7 | BJ | | 150-199, 275-299 |
| 38B | 22 | | PA | 8-0 | 25-53-15 | D10600 | A2 | | | | | | C00045 | 1 | D | | 050-099 |
| 38B | 22 | | PA | 7-0 | 25-53-15 | D10600 | A2 | | | | | | C00045 | 1 | D | | 150-199, 275-299 |
| 38D | 22 | | PA | 3-0 | 25-53-15 | D10600 | X1 | | | | | | TB0306Z | 7 | BJ | | 050-099 |
| 38D | 22 | | PA | 2-0 | 25-53-15 | D10600 | X1 | | | | | | TB0306Z | 7 | BJ | | 150-199, 275-299 |
| 38E | 22 | | PA | 3-0 | 25-53-15 | D10600 | X2 | | | | | | TB0306Z | 8 | BJ | | 050-099 |
| 38E | 22 | | PA | 2-0 | 25-53-15 | D10600 | X2 | | | | | | TB0306Z | 8 | BJ | | 150-199, 275-299 |
| 39A | 22 | | PA | 6-0 | 25-53-16 | D10608 | A1 | | | | | | TB0112H | 1 | 2 | | 050-099 |
| 39A | 22 | | PA | 7-0 | 25-53-16 | D10608 | A1 | | | | | | TB0112Z | 1 | BJ | | 150-199, 275-299 |
| 39B | 22 | | PA | 8-0 | 25-53-16 | D10608 | A2 | | | | | | C00049 | 1 | D | | 050-099 |
| 39B | 22 | | PA | 7-0 | 25-53-16 | D10608 | A2 | | | | | | C00049 | 1 | D | | 150-199, 275-299 |
| 39D | 22 | | PA | 3-0 | 25-53-16 | D10608 | X1 | | | | | | TB0306Z | 10 | BJ | | 050-099 |
| 39D | 22 | | PA | 2-0 | 25-53-16 | D10608 | X1 | | | | | | TB0306Z | 10 | BJ | | 150-199, 275-299 |
| 39E | 22 | | PA | 3-0 | 25-53-16 | D10608 | X2 | | | | | | TB0306Z | 9 | BJ | | 050-099 |
| 39E | 22 | | PA | 2-0 | 25-53-16 | D10608 | X2 | | | | | | TB0306Z | 9 | BJ | | 150-199, 275-299 |
| 40B | 22 | | PA | 3-0 | 25-53-15 | D10592 | 2 | | | | | | TB0306Z | 12 | BJ | | 050-099 |
| 40B | 22 | | PA | 2-0 | 25-53-15 | D10592 | 2 | | | | | | TB0306Z | 12 | BJ | | 150-199, 275-299 |
| 40C | 22 | | PA | 3-0 | 25-53-15 | D10592 | 3 | | | | | | TB0306Z | 8 | BJ | | 050-099 |
| 40C | 22 | | PA | 2-0 | 25-53-15 | D10592 | 3 | | | | | | TB0306Z | 8 | BJ | | 150-199, 275-299 |
| 40E | 22 | | PA | 3-0 | 25-53-15 | D10592 | 5 | | | | | | TB0306Z | 7 | BJ | | 050-099 |
| 40E | 22 | | PA | 2-0 | 25-53-15 | D10592 | 5 | | | | | | TB0306Z | 7 | BJ | | 150-199, 275-299 |
| 40G | 22 | | PA | 3-0 | 25-53-15 | D10592 | 7 | | | | | | TB0306Y | A001 | BJ | | 050-099 |
| 40G | 22 | | PA | 2-0 | 25-53-15 | D10592 | 7 | | | | | | TB0306Y | A001 | BJ | | 150-199, 275-299 |
| 41B | 22 | | PA | 3-0 | 25-53-15 | D10594 | 2 | | | | | | TB0306Z | 12 | BJ | | 050-099 |
| 41B | 22 | | PA | 2-0 | 25-53-15 | D10594 | 2 | | | | | | TB0306Z | 12 | BJ | | 150-199, 275-299 |
| 41C | 22 | | PA | 3-0 | 25-53-15 | D10594 | 3 | | | | | | TB0306Z | 8 | BJ | | 050-099 |
| 41C | 22 | | PA | 2-0 | 25-53-15 | D10594 | 3 | | | | | | TB0306Z | 8 | BJ | | 150-199, 275-299 |
| 41E | 22 | | PA | 3-0 | 25-53-15 | D10594 | 5 | | | | | | TB0306Z | 7 | BJ | | 050-099 |
| 41E | 22 | | PA | 2-0 | 25-53-15 | D10594 | 5 | | | | | | TB0306Z | 7 | BJ | | 150-199, 275-299 |
| 41G | 22 | | PA | 3-0 | 25-53-15 | D10594 | 7 | | | | | | TB0306Y | A002 | BJ | | 050-099 |
| 41G | 22 | | PA | 2-0 | 25-53-15 | D10594 | 7 | | | | | | TB0306Y | A002 | BJ | | 150-199, 275-299 |
| 42B | 22 | | PA | 3-0 | 25-53-15 | D10596 | 2 | | | | | | TB0306Z | 12 | BJ | | 050-099 |
| 42B | 22 | | PA | 2-0 | 25-53-15 | D10596 | 2 | | | | | | TB0306Z | 12 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 41

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | |
| 42C | 22 | | PA | 3-0 | 25-53-15 | D10596 | | | 3 | | TB0306Z | 8 | BJ | | 050-099 |
| 42C | 22 | | PA | 2-0 | 25-53-15 | D10596 | | | 3 | | TB0306Z | 8 | BJ | | 150-199, 275-299 |
| 42E | 22 | | PA | 3-0 | 25-53-15 | D10596 | | | 5 | | TB0306Z | 7 | BJ | | 050-099 |
| 42E | 22 | | PA | 2-0 | 25-53-15 | D10596 | | | 5 | | TB0306Z | 7 | BJ | | 150-199, 275-299 |
| 42G | 22 | | PA | 3-0 | 25-53-15 | D10596 | | | 7 | | TB0306Y | A003 | BJ | | 050-099 |
| 42G | 22 | | PA | 2-0 | 25-53-15 | D10596 | | | 7 | | TB0306Y | A003 | BJ | | 150-199, 275-299 |
| 43B | 22 | | PA | 3-0 | 25-53-15 | D10598 | | | 2 | | TB0306Z | 12 | BJ | | 050-099 |
| 43B | 22 | | PA | 2-0 | 25-53-15 | D10598 | | | 2 | | TB0306Z | 12 | BJ | | 150-199, 275-299 |
| 43C | 22 | | PA | 3-0 | 25-53-15 | D10598 | | | 3 | | TB0306Z | 8 | BJ | | 050-099 |
| 43C | 22 | | PA | 2-0 | 25-53-15 | D10598 | | | 3 | | TB0306Z | 8 | BJ | | 150-199, 275-299 |
| 43E | 22 | | PA | 3-0 | 25-53-15 | D10598 | | | 5 | | TB0306Z | 7 | BJ | | 050-099 |
| 43E | 22 | | PA | 2-0 | 25-53-15 | D10598 | | | 5 | | TB0306Z | 7 | BJ | | 150-199, 275-299 |
| 43G | 22 | | PA | 3-0 | 25-53-15 | D10598 | | | 7 | | TB0306Y | A004 | BJ | | 050-099 |
| 43G | 22 | | PA | 2-0 | 25-53-15 | D10598 | | | 7 | | TB0306Y | A004 | BJ | | 150-199, 275-299 |
| 44B | 22 | | PA | 2-0 | 25-53-16 | D10602 | | | 2 | | TB0306Z | 11 | BJ | | ALL |
| 44C | 22 | | PA | 3-0 | 25-53-16 | D10602 | | | 3 | | TB0306Z | 9 | BJ | | 050-099 |
| 44C | 22 | | PA | 2-0 | 25-53-16 | D10602 | | | 3 | | TB0306Z | 9 | BJ | | 150-199, 275-299 |
| 44E | 22 | | PA | 3-0 | 25-53-16 | D10602 | | | 5 | | TB0306Z | 10 | BJ | | 050-099 |
| 44E | 22 | | PA | 2-0 | 25-53-16 | D10602 | | | 5 | | TB0306Z | 10 | BJ | | 150-199, 275-299 |
| 44G | 22 | | PA | 3-0 | 25-53-16 | D10602 | | | 7 | | TB0306Y | C001 | BJ | | 050-099 |
| 44G | 22 | | PA | 7-0 | 25-53-16 | D10602 | | | 7 | | TB0306Y | C001 | BJ | | 150-199, 275-299 |
| 45B | 22 | | PA | 2-0 | 25-53-16 | D10604 | | | 2 | | TB0306Z | 11 | BJ | | ALL |
| 45C | 22 | | PA | 3-0 | 25-53-16 | D10604 | | | 3 | | TB0306Z | 9 | BJ | | 050-099 |
| 45C | 22 | | PA | 2-0 | 25-53-16 | D10604 | | | 3 | | TB0306Z | 9 | BJ | | 150-199, 275-299 |
| 45E | 22 | | PA | 3-0 | 25-53-16 | D10604 | | | 5 | | TB0306Z | 10 | BJ | | 050-099 |
| 45E | 22 | | PA | 2-0 | 25-53-16 | D10604 | | | 5 | | TB0306Z | 10 | BJ | | 150-199, 275-299 |
| 45G | 22 | | PA | 5-0 | 25-53-16 | D10604 | | | 7 | | D11620 | 8 | | | 050-099 |
| 45G | 22 | | PA | 7-0 | 25-53-16 | D10604 | | | 7 | | D11620 | 8 | | | 150-199, 275-299 |
| 46B | 22 | | PA | 2-0 | 25-53-16 | D10606 | | | 2 | | TB0306Z | 11 | BJ | | ALL |
| 46C | 22 | | PA | 3-0 | 25-53-16 | D10606 | | | 3 | | TB0306Z | 9 | BJ | | 050-099 |
| 46C | 22 | | PA | 2-0 | 25-53-16 | D10606 | | | 3 | | TB0306Z | 9 | BJ | | 150-199, 275-299 |
| 46E | 22 | | PA | 3-0 | 25-53-16 | D10606 | | | 5 | | TB0306Z | 10 | BJ | | 050-099 |
| 46E | 22 | | PA | 2-0 | 25-53-16 | D10606 | | | 5 | | TB0306Z | 10 | BJ | | 150-199, 275-299 |
| 46G | 22 | | PA | 3-0 | 25-53-16 | D10606 | | | 7 | | TB0306Z | 13 | BJ | | 050-099 |
| 46G | 22 | | PA | 2-0 | 25-53-16 | D10606 | | | 7 | | TB0306Z | 13 | BJ | | 150-199, 275-299 |
| 47B | 22 | | PA | 2-0 | 25-53-17 | D10610 | | | 2 | | TB0306Z | 11 | BJ | | ALL |
| 47C | 22 | | PA | 3-0 | 25-53-17 | D10610 | | | 3 | | TB0306Z | 9 | BJ | | 050-099 |
| 47C | 22 | | PA | 7-0 | 25-53-17 | TB0110Z | | | 40 | BJ | D10610 | 3 | | | 150-199, 275-299 |
| 47E | 22 | | PA | 3-0 | 25-53-17 | D10610 | | | 5 | | TB0306Z | 10 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 42

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 47E | 22 | | PA | 2-0 | 25-53-17 | D10610 | | 5 | | | | | TB0306Z | 10 | BJ | | 150-199, 275-299 |
| 47G | 22 | | PA | 2-0 | 25-53-17 | D10610 | | 7 | | | | | TB0306Y | C004 | BJ | | 150-199, 275-299 |
| 48B | 22 | | PA | 2-0 | 25-53-17 | D10612 | | 2 | | | | | TB0306Z | 11 | BJ | | ALL |
| 48C | 22 | | PA | 3-0 | 25-53-17 | D10612 | | 3 | | | | | TB0306Z | 9 | BJ | | 050-099 |
| 48C | 22 | | PA | 7-0 | 25-53-17 | D10612 | | 3 | | | | | TB0110Z | 40 | BJ | | 150-199, 275-299 |
| 48E | 22 | | PA | 3-0 | 25-53-17 | D10612 | | 5 | | | | | TB0306Z | 10 | BJ | | 050-099 |
| 48E | 22 | | PA | 2-0 | 25-53-17 | D10612 | | 5 | | | | | TB0306Z | 10 | BJ | | 150-199, 275-299 |
| 48G | 22 | | PA | 2-0 | 25-53-17 | D10612 | | 7 | | | | | TB0306Y | C005 | BJ | | 150-199, 275-299 |
| 49B | 22 | | PA | 2-0 | 25-53-17 | D10614 | | 2 | | | | | TB0306Z | 11 | BJ | | ALL |
| 49C | 22 | | PA | 3-0 | 25-53-17 | D10614 | | 3 | | | | | TB0306Z | 9 | BJ | | 050-099 |
| 49C | 22 | | PA | 7-0 | 25-53-17 | D10614 | | 3 | | | | | TB0110Z | 40 | BJ | | 150-199, 275-299 |
| 49E | 22 | | PA | 3-0 | 25-53-17 | D10614 | | 5 | | | | | TB0306Z | 10 | BJ | | 050-099 |
| 49E | 22 | | PA | 2-0 | 25-53-17 | D10614 | | 5 | | | | | TB0306Z | 10 | BJ | | 150-199, 275-299 |
| 49G | 22 | | PA | 3-0 | 25-53-17 | D10614 | | 7 | | | | | TB0306Y | C006 | BJ | | 050-099 |
| 49G | 22 | | PA | 2-0 | 25-53-17 | D10614 | | 7 | | | | | TB0306Y | C006 | BJ | | 150-199, 275-299 |
| 500 | 22 | | PA | 3-0 | 25-53-13 | D02444 | | 11 | | | | | TB0110Z | 39 | BJ | | 150-199, 275-299 |
| 501 | 22 | | PA | 3-0 | 25-53-11 | D05216J | | 1 | | | | | TB0114H | 3 | 2 | | 050-099 |
| 501 | 22 | | PA | 4-0 | 25-53-11 | D05216J | | 1 | | | | | TB0112Z | 5 | BJ | | 150-199, 275-299 |
| 502 | 20 | | PA | 5-0 | 25-53-11 | D05216J | | 2 | | | | | D02466 | 5 | | | 050-099 |
| 502 | 20 | | PA | 4-0 | 25-53-11 | D05216J | | 2 | | | | | D02466 | 5 | | | 150-199, 275-299 |
| 503 | 20 | | PA | 3-0 | 25-53-11 | D05216J | | 3 | | | | | TB0114H | 1 | 2 | | 050-099 |
| 503 | 20 | | PA | 4-0 | 25-53-11 | D05216J | | 3 | | | | | TB0112Z | 9 | BJ | | 150-199, 275-299 |
| 504 | 22 | | PA | 4-0 | 25-53-13 | D05216J | | 4 | | | | | TB0110G | 13 | 2 | | 050-099 |
| 504 | 22 | | PA | 4-0 | 25-53-13 | D05216J | | 4 | | | | | TB0110Y | A053 | BJ | | 150-199, 275-299 |
| 507 | 22 | | PA | 3-0 | 25-53-14 | D01288 | | A1 | | | | | TB0112Y | A029 | BJ | | 050-099 |
| 508 | 22 | | PA | 4-0 | 25-53-17 | D05216J | | 8 | | | | | TB0112G | 32 | 2 | | ALL |
| 509 | 22 | | PA | 5-0 | 25-53-14 | TB0112Y | | A029 | BJ | | | | D05224J | 15 | | | 050-099 |
| 50B | 22 | | PA | 2-0 | 25-53-17 | D10616 | | 2 | | | | | TB0306Z | 11 | BJ | | ALL |
| 50C | 22 | | PA | 3-0 | 25-53-17 | D10616 | | 3 | | | | | TB0306Z | 8 | BJ | | 050-099 |
| 50C | 22 | | PA | 7-0 | 25-53-17 | D10616 | | 3 | | | | | TB0110Z | 50 | BJ | | 150-199, 275-299 |
| 50D | 22 | | PA | 4-0 | 25-53-13 | TB0112Z | | 27 | BJ | | | | TB0110D | A006 | 2 | | 050-099 |
| 50E | 22 | | PA | 3-0 | 25-53-17 | D10616 | | 5 | | | | | TB0306Z | 10 | BJ | | 050-099 |
| 50E | 22 | | PA | 2-0 | 25-53-17 | D10616 | | 5 | | | | | TB0306Z | 10 | BJ | | 150-199, 275-299 |
| 50F | 22 | | PA | 1-0 | 25-53-15 | TB0112D | | C028 | 2 | | | | TB0112D | C025 | 2 | | 050-099 |
| 50G | 22 | | PA | 3-0 | 25-53-17 | D10616 | | 7 | | | | | TB0306Y | A006 | BJ | | 050-099 |
| 50G | 22 | | PA | 2-0 | 25-53-17 | D10616 | | 7 | | | | | TB0306Y | A006 | BJ | | 150-199, 275-299 |
| 50H | 22 | | PA | 1-0 | 25-53-15 | TB0112D | | A025 | 2 | | | | TB0112Z | 27 | BJ | | 050-099 |
| 50J | 22 | | PA | 7-0 | 25-53-16 | TB0110D | | C006 | 2 | | | | TB0306Z | 13 | BJ | | 050-099 |
| 510 | 22 | | PA | 5-0 | 25-53-14 | TB0112Y | | C029 | BJ | | | | D05224J | 13 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 43

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|------|----|---|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | | | |
| 511 | 22 | PA | | | 4-0 | 25-53-11 | D05216J | | 11 | | | | | | C00076 | 1 | D | * | 050-099 |
| 511 | 20 | PA | | | 4-0 | 25-53-11 | D05216J | | 11 | | | | | | C00076 | 1 | D | * | 150-199, 275-299 |
| 512 | 22 | PA | | | 5-0 | 25-53-14 | D05224J | | 14 | | | | | | TB0112Y | C029 | BJ | | 050-099 |
| 513 | 22 | PA | | | 5-0 | 25-53-13 | D05216J | | 13 | | | | | | TB0110G | 30 | 2 | | 050-099 |
| 513 | 22 | PA | | | 4-0 | 25-53-13 | TB0110G | | 32 | | | | | | D01288 | X1 | | | 150-199, 275-299 |
| 514 | 22 | PA | | | 1-0 | 25-53-14 | TB0112Y | | A013 | | 2 | | | | D01684 | X1 | | | 050-099 |
| 514 | 22 | PA | | | 4-0 | 25-53-14 | D11150 | | 1 | | | | | | D01684 | X1 | | | 150-199, 275-299 |
| 515 | 22 | PA | | | 5-0 | 25-53-14 | TB0110G | | 26 | | 2 | | | | D01686 | X1 | | | 050-099 |
| 515 | 22 | PA | | | 4-0 | 25-53-14 | D11150 | | 5 | | | | | | D01686 | X1 | | | 150-199, 275-299 |
| 516 | 22 | PA | | | 5-0 | 25-53-13 | D05216J | | 16 | | | | | | TB0110G | 1 | 2 | | 050-099 |
| 516 | 22 | PA | | | 5-0 | 25-53-13 | D05216J | | 16 | | | | | | TB0110Z | 1 | BJ | | 150-199, 275-299 |
| 517 | 22 | PA | | | 5-0 | 25-53-13 | D05216J | | 17 | | | | | | TB0110G | 2 | 2 | | 050-099 |
| 517 | 22 | PA | | | 5-0 | 25-53-13 | D05216J | | 17 | | | | | | TB0110Z | 2 | BJ | | 150-199, 275-299 |
| 518 | 22 | PA | | | 5-0 | 25-53-15 | D05216J | | 18 | | | | | | D02444 | 7 | | | 050-099 |
| 518 | 22 | PA | | | 4-0 | 25-53-14 | D05216J | | 18 | | | | | | TB0112Z | 34 | BJ | | 150-199, 275-299 |
| 519 | 22 | PA | | | 3-0 | 25-53-14 | D01288 | | C3 | | | | | | TB0112G | 11 | 2 | | 050-099 |
| 520 | 22 | PA | | | 5-0 | 25-53-14 | D05224J | | 9 | | | | | | TB0112G | 11 | 2 | | 050-099 |
| 521 | 20 | PA | | | 3-0 | 25-53-11 | D05614J | | 1 | | | | | | TB0114H | 1 | 2 | | 050-099 |
| 521 | 20 | PA | | | 4-0 | 25-53-11 | D05614J | | 1 | | | | | | TB0112Z | 9 | BJ | | 150-199, 275-299 |
| 522 | 20 | PA | | | 3-0 | 25-53-11 | D05614J | | 2 | | | | | | TB0114D | C | 2 | | 050-099 |
| 522 | 20 | PA | | | 2-0 | 25-53-11 | D05614J | | 2 | | | | | | TB0114D | C002 | 2 | | 150-199, 275-299 |
| 523 | 24 | PK | | | 3-0 | 52-34-12 | D05614J | | 3 | | | | | | TB0114G | 7 | 2 | | 050-099 |
| 523 | 24 | PK | | | 5-0 | 52-34-12 | D05614J | | 3 | | | | | | TB0110G | 5 | 2 | | 150-199, 275-299 |
| 524 | 24 | PK | | | 4-0 | 52-34-12 | D05614J | | 4 | | | | | | D02506 | X2 | | | ALL |
| 525 | 24 | PK | | | 4-0 | 52-34-12 | D05614J | | 5 | | | | | | D02508 | X2 | | | ALL |
| 526 | 24 | PK | | | 3-0 | 52-34-12 | D05614J | | 6 | | | | | | D05886J | 6 | | | 050-099 |
| 526 | 24 | PK | | | 2-0 | 52-34-12 | D05614J | | 6 | | | | | | D05886J | 6 | | | 150-199, 275-299 |
| 527 | 24 | PK | | | 3-0 | 52-34-12 | D05614J | | 7 | | | | | | R00035 | C | 2 | | 050-099 |
| 527 | 24 | PK | | | 2-0 | 52-34-12 | D05614J | | 7 | | | | | | TB0114D | C001 | 2 | | 150-199, 275-299 |
| 528 | 24 | PK | | | 5-0 | 52-34-12 | D05614J | | 8 | | | | | | D02502 | X2 | | | 050-099 |
| 528 | 24 | PK | | | 4-0 | 52-34-12 | D05614J | | 8 | | | | | | D02502 | X2 | | | 150-199, 275-299 |
| 529 | 24 | PK | | | 4-0 | 52-34-12 | D05614J | | 9 | | | | | | D02504 | X2 | | | ALL |
| 530 | 22 | PA | | | 3-0 | 25-53-13 | D05614J | | 10 | | | | | | TB0114H | 5 | 2 | | 050-099 |
| 530 | 22 | PA | | | 4-0 | 25-53-13 | D05614J | | 10 | | | | | | TB0110Z | 39 | BJ | | 150-199, 275-299 |
| 531 | 22 | PA | | | 5-0 | 25-53-13 | TB0110H | | 39 | | 2 | | | | TB0114H | 5 | 2 | | 050-099 |
| 531 | 22 | PA | | | 1-0 | 25-53-13 | TB0110Z | | 40 | | BJ | | | | TB0110Z | 39 | BJ | | 150-199, 275-299 |
| 532 | 22 | PA | | | 5-0 | 25-53-13 | TB0112H | | 5 | | 2 | | | | TB0114H | 5 | 2 | | 050-099 |
| 532 | 22 | PA | | | 1-0 | 25-53-13 | TB0110Z | | 41 | | BJ | | | | TB0110Z | 42 | BJ | | 150-199, 275-299 |
| 533 | 22 | PA | | | 7-0 | 25-53-14 | D02432 | | C2 | | | | | | TB0306Y | C005 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 44

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 534 | 22 | | PA | 3-0 | 25-53-17 | D01608 | | B2 | | | | | TB0112H | 9 | 2 | | 050-099 |
| 534 | 22 | | PA | 4-0 | 25-53-17 | D01608 | | B2 | | | | | TB0112Z | 8 | BJ | | 150-199, 275-299 |
| 535 | 22 | | PA | 5-0 | 25-53-14 | D05614J | | 15 | | | | | TB0110H | 43 | 2 | | 050-099 |
| 536 | 22 | | PA | 4-0 | 25-53-17 | D01608 | | A3 | | | | | D05218J | 32 | | | ALL |
| 537 | 20 | | PA | 5-0 | 33-37-11 | TB0114H | | 1 | 2 | | | | D02632 | X1 | | | 050-099 |
| 537 | 20 | | PA | 4-0 | 33-37-11 | TB0112Z | | 9 | BJ | | | | D02632 | X1 | | | 150-199, 275-299 |
| 538 | 20 | | PA | 5-0 | 33-37-11 | D05614J | | 17 | | | | | D02632 | X2 | | | 050-099 |
| 538 | 20 | | PA | 4-0 | 33-37-11 | D05614J | | 17 | | | | | D02632 | X2 | | | 150-199, 275-299 |
| 539 | 22 | | PA | 4-0 | 25-53-13 | D02444 | | 2 | | | | | TB0110G | 35 | 2 | | 050-099 |
| 539 | 22 | | PA | 4-0 | 25-53-13 | D02444 | | 2 | | | | | TB0110Z | 35 | BJ | | 150-199, 275-299 |
| 540 | 22 | | PA | 5-0 | 25-53-14 | D05224J | | 23 | | | | | TB0110G | 29 | 2 | | 050-099 |
| 540 | 22 | | PA | 1-0 | 25-53-13 | TB0114D | | C004 | 2 | | | | TB0114D | C003 | 2 | | 150-199, 275-299 |
| 541 | 22 | | PA | 3-0 | 25-53-13 | S00383 | | 1 | C | | | | L00619 | =P | \$ | | 050-099 |
| 542 | 22 | | PA | 6-0 | 25-53-11 | S00383 | | 2 | C | | * | | TB0114H | 3 | 2 | | 050-099 |
| 543 | 22 | | PA | 6-0 | 25-53-13 | TB0110D | | C037 | 2 | | | | S00383 | 5 | C | | 050-099 |
| 544 | 22 | | PA | 1-0 | 25-53-13 | S00675 | | 2 | B | | | | L00826 | =G | \$ | * | 150-199, 275-299 |
| 545 | 22 | | PA | 2-0 | 25-53-14 | TB0110H | | 20 | 2 | | | | TB0110G | 31 | 2 | | 050-099 |
| 545 | 22 | | PA | 2-0 | 25-53-13 | L00826 | | =P | \$ | | * | | L00812 | =P | \$ | | 150-199, 275-299 |
| 546 | 22 | | PA | 3-0 | 25-53-13 | S00383 | | 3 | C | | | | L00149 | =P | \$ | | 050-099 |
| 546 | 22 | | PA | 1-0 | 25-53-13 | S00675 | | 5 | B | | * | | L00813 | =G | \$ | | 150-199, 275-299 |
| 547 | 22 | | PA | 5-0 | 25-53-14 | D01284 | | A1 | | | | | TB0110G | 33 | 2 | | 050-099 |
| 547 | 22 | | PA | 6-0 | 25-53-13 | TB0112Z | | 10 | BJ | | | | S00675 | 4 | B | | 150-199, 275-299 |
| 548 | 22 | | PA | 7-0 | 25-53-13 | S00383 | | 4 | C | | | | TB0110H | 52 | 2 | | 050-099 |
| 549 | 22 | | PA | 5-0 | 25-53-14 | D01284 | | A2 | | | | | TB0110G | 32 | 2 | | 050-099 |
| 549 | 22 | | PA | 2-0 | 25-53-13 | L00814 | | =P | \$ | | * | | L00826 | =P | \$ | * | 150-199, 275-299 |
| 550 | 22 | | PA | 5-0 | 25-53-13 | D02444 | | 1 | | | | | TB0110G | 1 | 2 | | 050-099 |
| 550 | 22 | | PA | 6-0 | 25-53-13 | D02444 | | 1 | | | | | TB0110Z | 1 | BJ | | 150-199, 275-299 |
| 551 | 22 | | PA | 5-0 | 25-53-13 | D02444 | | 13 | | | | | TB0110H | 54 | 2 | | 050-099 |
| 551 | 22 | | PA | 6-0 | 25-53-13 | D02444 | | 13 | | | | | TB0110G | 3 | 2 | | 150-199, 275-299 |
| 552 | 22 | | PA | 5-0 | 25-53-13 | D02444 | | 5 | | | | | TB0110G | 2 | 2 | | 050-099 |
| 552 | 22 | | PA | 6-0 | 25-53-13 | D02444 | | 5 | | | | | TB0110Z | 2 | BJ | | 150-199, 275-299 |
| 553 | 22 | | PA | 5-0 | 25-53-13 | D02444 | | 3 | | | | | TB0110G | 4 | 2 | | 050-099 |
| 553 | 22 | | PA | 6-0 | 25-53-13 | D02444 | | 3 | | | | | TB0110G | 4 | 2 | | 150-199, 275-299 |
| 554 | 22 | | PA | 5-0 | 25-53-13 | D02438 | | X2 | | | | | TB0110Z | 40 | BJ | | 150-199, 275-299 |
| 555 | 22 | | PA | 5-0 | 25-53-13 | D02444 | | 9 | | | | | TB0110G | 7 | 2 | | 050-099 |
| 555 | 22 | | PA | 6-0 | 25-53-13 | D02444 | | 9 | | | | | TB0110G | 8 | 2 | | 150-199, 275-299 |
| 556 | 22 | | PA | 5-0 | 25-53-15 | D02444 | | 14 | | | | | TB0110G | 5 | 2 | | 050-099 |
| 556 | 22 | | PA | 1-0 | 25-53-15 | D02444 | | 14 | | | | | D02458 | X1 | | | 150-199, 275-299 |
| 557 | 22 | | PA | 2-0 | 25-53-15 | D02444 | | 8 | | | | | TB0112D | A028 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 45

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 557 | 22 | PA | | 5-0 | 25-53-15 | D02444 | | 8 | | | | | TB0114D | A006 | 2 | | 150-199, 275-299 |
| 558 | 22 | PA | | 6-0 | 25-53-13 | D02444 | | 10 | | | | | TB0110H | 12 | 2 | | 150-199, 275-299 |
| 559 | 22 | PA | | 5-0 | 25-53-13 | D02444 | | 12 | | | | | TB0110H | 39 | 2 | | 050-099 |
| 559 | 22 | PA | | 3-0 | 25-53-13 | D02444 | | 12 | | | | | TB0110Z | 40 | BJ | | 150-199, 275-299 |
| 560 | 22 | PA | | 5-0 | 25-53-13 | D02444 | | 4 | | | | | TB0110G | 36 | 2 | | 050-099 |
| 560 | 22 | PA | | 5-0 | 25-53-13 | D02444 | | 4 | | | | | TB0110Z | 36 | BJ | | 150-199, 275-299 |
| 561 | 22 | PA | | 3-0 | 25-53-13 | S00384 | | 4 | C | | | | L00437 | =P | \$ | | 050-099 |
| 562 | 22 | PA | | 2-0 | 25-53-11 | S00384 | | 2 | C | * | | | S00383 | 2 | C | * | 050-099 |
| 563 | 22 | PA | | 3-0 | 25-53-13 | S00384 | | 1 | C | | | | L00438 | =P | \$ | | 050-099 |
| 564 | 22 | PA | | 7-0 | 25-53-13 | S00384 | | 8 | C | * | | | TB0110D | C012 | 2 | | 050-099 |
| 565 | 22 | PA | | 2-0 | 25-53-13 | S00677 | | 1 | B | * | | | S00698 | 2 | B | * | 150-199, 275-299 |
| 566 | 22 | PA | | 6-0 | 25-53-13 | L00149 | | =G | \$ | * | | | TB0114H | 5 | 2 | | 050-099 |
| 566 | 22 | PA | | 3-0 | 25-53-13 | L00814 | | =G | \$ | | | | S00563 | 8 | C | | 150-199, 275-299 |
| 567 | 22 | PA | | 3-0 | 25-53-13 | L00149 | | =G | \$ | * | | | L00619 | =G | \$ | * | 050-099 |
| 567 | 22 | PA | | 6-0 | 25-53-13 | TB0112Z | | 10 | BJ | | | | L00814 | =P | \$ | * | 150-199, 275-299 |
| 568 | 22 | PA | | 6-0 | 25-53-13 | TB0112Z | | 10 | BJ | | | | L00813 | =P | \$ | | 150-199, 275-299 |
| 569 | 22 | PA | | 3-0 | 25-53-13 | L00437 | | =G | \$ | * | | | L00145 | =G | \$ | * | 050-099 |
| 570 | 22 | PA | | 3-0 | 25-53-13 | L00438 | | =G | \$ | | | | L00437 | =G | \$ | * | 050-099 |
| 571 | 22 | PA | | 3-0 | 25-53-13 | D02468 | | 2 | | | | | TB0110H | 50 | 2 | | 050-099 |
| 572 | 22 | PA | | 2-0 | 25-53-13 | D02468 | | 5 | | | | | TB0110G | 7 | 2 | | 050-099 |
| 573 | 22 | PA | | 2-0 | 25-53-15 | D02468 | | 3 | | | | | TB0110H | 39 | 2 | | 050-099 |
| 574 | 22 | PA | | 2-0 | 25-53-15 | D02468 | | 7 | | | | | TB0110G | 5 | 2 | | 050-099 |
| 575 | 22 | PA | | 6-0 | 25-53-15 | D02458 | | X1 | | | | | S00387 | 2 | C | | 050-099 |
| 576 | 22 | PA | | 3-0 | 25-53-15 | D02458 | | X2 | | | | | TB0112H | 5 | 2 | | 050-099 |
| 576 | 22 | PA | | 3-0 | 25-53-15 | D02458 | | X2 | | | | | TB0110Z | 41 | BJ | | 150-199, 275-299 |
| 577 | 22 | PA | | 7-0 | 25-53-15 | TB0110G | | 5 | 2 | | | | S00387 | 1 | C | | 050-099 |
| 578 | 22 | PA | | 3-0 | 25-53-16 | D02454 | | X2 | | | | | TB0112H | 5 | 2 | | 050-099 |
| 578 | 22 | PA | | 3-0 | 25-53-16 | D02454 | | X2 | | | | | TB0110Z | 38 | BJ | | 150-199, 275-299 |
| 579 | 22 | PA | | 3-0 | 25-53-16 | D02456 | | X2 | | | | | TB0112H | 5 | 2 | | 050-099 |
| 579 | 22 | PA | | 3-0 | 25-53-16 | D02456 | | X2 | | | | | TB0110Z | 38 | BJ | | 150-199, 275-299 |
| 580 | 22 | PA | | 2-0 | 25-53-13 | TB0110H | | 39 | 2 | | | | TB0110H | 50 | 2 | | 050-099 |
| 580 | 22 | PA | | 1-0 | 25-53-13 | TB0110Z | | 40 | BJ | | | | TB0110Z | 41 | BJ | | 150-199, 275-299 |
| 581 | 22 | PA | | 3-0 | 25-53-13 | D02470 | | 2 | | | | | TB0110H | 50 | 2 | | 050-099 |
| 582 | 22 | PA | | 6-0 | 25-53-13 | D02470 | | 5 | | | | | S00384 | 9 | C | | 050-099 |
| 583 | 22 | PA | | 3-0 | 25-53-15 | D02470 | | 3 | | | | | TB0110H | 39 | 2 | | 050-099 |
| 584 | 22 | PA | | 3-0 | 25-53-15 | D02470 | | 7 | | | | | TB0112D | C028 | 2 | | 050-099 |
| 585 | 22 | PA | | 6-0 | 25-53-15 | D02460 | | X1 | | | | | S00388 | 2 | C | | 050-099 |
| 586 | 22 | PA | | 2-0 | 25-53-15 | D02460 | | X2 | | | | | TB0112H | 5 | 2 | | 050-099 |
| 586 | 22 | PA | | 3-0 | 25-53-15 | D02460 | | X2 | | | | | TB0110Z | 41 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 46

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 587 | 22 | | PA | 5-0 | 25-53-15 | TB0112D | C025 | 2 | | | | | S00388 | 1 | C | | 050-099 |
| 588 | 22 | | PA | 5-0 | 25-53-14 | D05224J | | 29 | | | | | D02456 | D2 | | | 050-099 |
| 589 | 20 | | PA | 2-0 | 25-53-11 | K00245 | | 11 | C | * | | | TB0114H | 1 | 2 | | 050-099 |
| 589 | 20 | | PA | 5-0 | 25-53-11 | K00245 | | 11 | C | * | | | TB0112Z | 9 | BJ | | 150-199, 275-299 |
| 590 | 20 | | PA | 4-0 | 25-53-11 | K00245 | | 12 | C | | | | TB0112G | 34 | 2 | | 050-099 |
| 590 | 20 | | PA | 5-0 | 25-53-11 | K00245 | | 12 | C | | | | TB0112G | 28 | 2 | | 150-199, 275-299 |
| 591 | 20 | | PA | 2-0 | 25-53-11 | K00245 | | 11 | C | * | | | K00245 | X1 | C | | 050-099 |
| 591 | 20 | | PA | 1-0 | 25-53-11 | K00245 | | 11 | C | * | | | K00245 | X1 | C | | 150-199, 275-299 |
| 592 | 20 | | PA | 5-0 | 25-53-11 | D02466 | | 2 | | | | | K00245 | X2 | C | | 050-099 |
| 592 | 20 | | PA | 4-0 | 25-53-11 | D02466 | | 2 | | | | | K00245 | X2 | C | | 150-199, 275-299 |
| 593 | 20 | | PA | 5-0 | 25-53-11 | D02466 | | 7 | | | | | TB0114H | 1 | 2 | | 050-099 |
| 593 | 20 | | PA | 4-0 | 25-53-11 | D02466 | | 7 | | | | | TB0112Z | 9 | BJ | | 150-199, 275-299 |
| 594 | 20 | | PA | 5-0 | 33-37-11 | D02528 | | X1 | | | | | TB0114H | 1 | 2 | | 050-099 |
| 594 | 20 | | PA | 4-0 | 33-37-11 | D02528 | | X1 | | | | | TB0112Z | 9 | BJ | | 150-199, 275-299 |
| 595 | 20 | | PA | 2-0 | 33-37-11 | D02466 | | 6 | | | | | D02528 | X2 | | | ALL |
| 596 | 20 | | PA | 3-0 | 33-37-11 | TB0110H | | 39 | 2 | | | | D02466 | 1 | | | 050-099 |
| 596 | 20 | | PA | 2-0 | 33-37-11 | TB0110Z | | 40 | BJ | | | | D02466 | 1 | | | 150-199, 275-299 |
| 597 | 22 | | PA | 3-0 | 25-53-17 | D02462 | | X2 | | | | | TB0112H | 5 | 2 | | 050-099 |
| 597 | 22 | | PA | 4-0 | 25-53-17 | D02462 | | X2 | | | | | TB0112G | 27 | 2 | | 150-199, 275-299 |
| 598 | 22 | | PA | 3-0 | 25-53-17 | D02464 | | X2 | | | | | TB0112H | 5 | 2 | | 050-099 |
| 598 | 22 | | PA | 4-0 | 25-53-17 | D02464 | | X2 | | | | | TB0112G | 27 | 2 | | 150-199, 275-299 |
| 599 | 22 | | PA | 4-0 | 25-53-17 | D01608 | | B3 | | | | | D05218J | 29 | | | 050-099 |
| 599 | 20 | | PA | 4-0 | 25-53-11 | D02466 | | 3 | | | | | TB0114D | A002 | 2 | | 150-199, 275-299 |
| 600 | 22 | | PA | 5-0 | 25-53-14 | D02448 | | 6 | | | | | TB0110H | 14 | 2 | | 050-099 |
| 600 | 22 | | PA | 3-0 | 25-53-14 | D02448 | | 6 | | | | | TB0110Z | 14 | BJ | | 150-199, 275-299 |
| 601 | 22 | | PA | 5-0 | 25-53-14 | D02448 | | 1 | | | | | D05224J | 1 | | | 050-099 |
| 601 | 22 | | PA | 4-0 | 25-53-14 | D02448 | | 1 | | | | | D05224J | 1 | | | 150-199, 275-299 |
| 602 | 22 | | PA | 5-0 | 25-53-14 | D02448 | | 2 | | | | | TB0110G | 22 | 2 | | 050-099 |
| 602 | 22 | | PA | 3-0 | 25-53-14 | D02448 | | 2 | | | | | TB0110G | 22 | 2 | | 150-199, 275-299 |
| 603 | 22 | | PA | 5-0 | 25-53-14 | D02448 | | 5 | | | | | D05224J | 2 | | | 050-099 |
| 603 | 22 | | PA | 4-0 | 25-53-14 | D02448 | | 5 | | | | | D05224J | 2 | | | 150-199, 275-299 |
| 604 | 22 | | PA | 3-0 | 25-53-14 | D01518 | | 5 | | | | | TB0112Y | A030 | BJ | | 050-099 |
| 605 | 22 | | PA | 3-0 | 25-53-14 | D01518 | | 2 | | | | | TB0112Y | C030 | BJ | | 050-099 |
| 606 | 22 | | PA | 3-0 | 25-53-14 | D01518 | | 7 | | | | | TB0112Y | C030 | BJ | | 050-099 |
| 608 | 22 | | PA | 5-0 | 25-53-13 | D02448 | | 7 | | | | | TB0110H | 54 | 2 | | 050-099 |
| 608 | 22 | | PA | 4-0 | 25-53-13 | D02448 | | 7 | | | | | TB0110G | 3 | 2 | | 150-199, 275-299 |
| 609 | 22 | | PA | 3-0 | 25-53-13 | D02448 | | 3 | | | | | TB0110D | A037 | 2 | | 050-099 |
| 609 | 22 | | PA | 4-0 | 25-53-13 | D02448 | | 3 | | | | | TB0114D | A004 | 2 | | 150-199, 275-299 |
| 610 | 22 | | PA | 5-0 | 25-53-14 | D02446 | | 6 | | | | | TB0110H | 14 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 47

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | |
| 610 | 22 | | PA | 4-0 | 25-53-14 | D02446 | | 6 | | | TB0110Z | 14 | BJ | | 150-199, 275-299 |
| 611 | 22 | | PA | 5-0 | 25-53-14 | D02446 | | 1 | | | D05224J | 4 | | | 050-099 |
| 611 | 22 | | PA | 4-0 | 25-53-14 | D02446 | | 1 | | | D05224J | 4 | | | 150-199, 275-299 |
| 612 | 22 | | PA | 5-0 | 25-53-14 | D02446 | | 2 | | | TB0110G | 22 | 2 | | 050-099 |
| 612 | 22 | | PA | 3-0 | 25-53-14 | D02446 | | 2 | | | TB0110G | 22 | 2 | | 150-199, 275-299 |
| 613 | 22 | | PA | 5-0 | 25-53-14 | D02446 | | 5 | | | D05224J | 5 | | | 050-099 |
| 613 | 22 | | PA | 4-0 | 25-53-14 | D02446 | | 5 | | | D05224J | 5 | | | 150-199, 275-299 |
| 614 | 22 | | PA | 5-0 | 25-53-14 | D02456 | | C1 | | | TB0110H | 43 | 2 | | 050-099 |
| 615 | 22 | | PA | 5-0 | 25-53-17 | D01390 | | B3 | | | D05218J | 28 | | | 050-099 |
| 615 | 22 | | PA | 4-0 | 25-53-17 | D01390 | | B3 | | | D05218J | 28 | | | 150-199, 275-299 |
| 616 | 22 | | PA | 5-0 | 25-53-17 | D01390 | | B1 | | | D05218J | 27 | | | 050-099 |
| 616 | 22 | | PA | 4-0 | 25-53-17 | D01390 | | B1 | | | D05218J | 27 | | | 150-199, 275-299 |
| 617 | 22 | | PA | 5-0 | 25-53-17 | D01390 | | A3 | | | D05218J | 31 | | | 050-099 |
| 617 | 22 | | PA | 4-0 | 25-53-17 | D01390 | | A3 | | | D05218J | 31 | | | 150-199, 275-299 |
| 618 | 22 | | PA | 5-0 | 25-53-13 | D02446 | | 7 | | | TB0110G | 4 | 2 | | 050-099 |
| 618 | 22 | | PA | 4-0 | 25-53-13 | D02446 | | 7 | | | TB0110G | 4 | 2 | | 150-199, 275-299 |
| 619 | 22 | | PA | 5-0 | 25-53-13 | D02446 | | 3 | | | TB0114D | A | 2 | | 050-099 |
| 619 | 22 | | PA | 4-0 | 25-53-13 | D02446 | | 3 | | | TB0114D | A003 | 2 | | 150-199, 275-299 |
| 620 | 22 | | PA | 3-0 | 25-53-14 | D02452 | | 6 | | | TB0110G | 27 | 2 | | 050-099 |
| 620 | 22 | | PA | 3-0 | 25-53-14 | D02452 | | 6 | | | TB0110Z | 14 | BJ | | 150-199, 275-299 |
| 621 | 22 | | PA | 5-0 | 25-53-14 | D02452 | | 1 | | | D05224J | 7 | | | 050-099 |
| 621 | 22 | | PA | 4-0 | 25-53-14 | D02452 | | 1 | | | D05224J | 7 | | | 150-199, 275-299 |
| 622 | 22 | | PA | 5-0 | 25-53-14 | D02452 | | 2 | | | TB0110G | 24 | 2 | | 050-099 |
| 622 | 22 | | PA | 3-0 | 25-53-14 | D02452 | | 2 | | | TB0110G | 24 | 2 | | 150-199, 275-299 |
| 623 | 22 | | PA | 5-0 | 25-53-14 | D02452 | | 5 | | | D05224J | 8 | | | 050-099 |
| 623 | 22 | | PA | 4-0 | 25-53-14 | D02452 | | 5 | | | D05224J | 8 | | | 150-199, 275-299 |
| 624 | 22 | | PA | 3-0 | 25-53-14 | TB0110Z | | 9 | BJ | | TB0110H | 16 | 2 | | 050-099 |
| 625 | 22 | | PA | 3-0 | 25-53-14 | TB0110H | | 18 | 2 | | TB0110G | 3 | 2 | | 050-099 |
| 628 | 22 | | PA | 5-0 | 25-53-13 | D02452 | | 7 | | | TB0110H | 54 | 2 | | 050-099 |
| 628 | 22 | | PA | 4-0 | 25-53-13 | D02452 | | 7 | | | TB0110G | 3 | 2 | | 150-199, 275-299 |
| 629 | 22 | | PA | 5-0 | 25-53-13 | D02452 | | 3 | | | TB0110H | 52 | 2 | | 050-099 |
| 629 | 22 | | PA | 4-0 | 25-53-13 | D02452 | | 3 | | | TB0110Z | 21 | BJ | | 150-199, 275-299 |
| 630 | 22 | | PA | 5-0 | 25-53-14 | D05224J | | 26 | | | TB0110G | 29 | 2 | | 050-099 |
| 630 | 22 | | PA | 4-0 | 25-53-14 | D02450 | | 6 | | | TB0110Z | 14 | BJ | | 150-199, 275-299 |
| 631 | 22 | | PA | 5-0 | 25-53-14 | D02450 | | 1 | | | D05224J | 11 | | | 050-099 |
| 631 | 22 | | PA | 4-0 | 25-53-14 | D02450 | | 1 | | | D05224J | 11 | | | 150-199, 275-299 |
| 632 | 22 | | PA | 5-0 | 25-53-14 | D02450 | | 2 | | | TB0110G | 24 | 2 | | 050-099 |
| 632 | 22 | | PA | 3-0 | 25-53-14 | D02450 | | 2 | | | TB0110G | 24 | 2 | | 150-199, 275-299 |
| 633 | 22 | | PA | 5-0 | 25-53-14 | D02450 | | 5 | | | D05224J | 12 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 48

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | | |
| 633 | 22 | | PA | 4-0 | 25-53-14 | D02450 | | | | 5 | | | | D05224J | 12 | | | 150-199, 275-299 |
| 634 | 22 | | PA | 5-0 | 25-53-17 | D01390 | | | | A1 | | | | D05218J | 30 | | | 050-099 |
| 634 | 22 | | PA | 4-0 | 25-53-17 | D01390 | | | | A1 | | | | D05218J | 30 | | | 150-199, 275-299 |
| 635 | 22 | | PA | 3-0 | 25-53-17 | D01390 | | | | B2 | | | | TB0112H | 9 | 2 | | 050-099 |
| 635 | 22 | | PA | 4-0 | 25-53-17 | D01390 | | | | B2 | | | | TB0112Z | 8 | BJ | | 150-199, 275-299 |
| 636 | 22 | | PA | 3-0 | 25-53-17 | D01390 | | | | A2 | | | | TB0112H | 9 | 2 | | 050-099 |
| 636 | 22 | | PA | 4-0 | 25-53-17 | D01390 | | | | A2 | | | | TB0112Z | 8 | BJ | | 150-199, 275-299 |
| 637 | 22 | | PA | 3-0 | 25-53-17 | D01390 | | | | X2 | | | | TB0112G | 33 | 2 | | ALL |
| 638 | 22 | | PA | 5-0 | 25-53-13 | D02450 | | | | 7 | | | | TB0110G | 4 | 2 | | 050-099 |
| 638 | 22 | | PA | 4-0 | 25-53-13 | D02450 | | | | 7 | | | | TB0110G | 4 | 2 | | 150-199, 275-299 |
| 639 | 22 | | PA | 5-0 | 25-53-13 | D02450 | | | | 3 | | | | TB0110H | 52 | 2 | | 050-099 |
| 639 | 22 | | PA | 4-0 | 25-53-13 | D02450 | | | | 3 | | | | TB0110Z | 21 | BJ | | 150-199, 275-299 |
| 640 | 22 | | PA | 5-0 | 25-53-14 | D02432 | | | | A2 | | | | TB0110G | 25 | 2 | | 050-099 |
| 640 | 22 | | PA | 2-0 | 25-53-14 | D02432 | | | | 6 | | | | TB0110G | 25 | 2 | | 150-199, 275-299 |
| 641 | 22 | | PA | 5-0 | 25-53-14 | D02432 | | | | A1 | | | | D05224J | 6 | | | 050-099 |
| 641 | 22 | | PA | 3-0 | 25-53-14 | D02432 | | | | 1 | | | | D05224J | 14 | | | 150-199, 275-299 |
| 642 | 22 | | PA | 2-0 | 25-53-14 | D02432 | | | | B2 | | | | TB0112Y | A030 | BJ | | 050-099 |
| 642 | 22 | | PA | 2-0 | 25-53-14 | D02432 | | | | 2 | | | | TB0110Z | 37 | BJ | | 150-199, 275-299 |
| 643 | 22 | | PA | 5-0 | 25-53-14 | D02432 | | | | B1 | | | | D05224J | 3 | | | 050-099 |
| 643 | 22 | | PA | 3-0 | 25-53-14 | D02432 | | | | 5 | | | | D05224J | 15 | | | 150-199, 275-299 |
| 644 | 20 | | PA | 3-0 | 25-53-17 | TB0112H | | | | 1 | 2 | | | TB0112H | 9 | 2 | | 050-099 |
| 644 | 22 | | PA | 2-0 | 25-53-17 | TB0112Z | | | | 1 | BJ | | | TB0112Z | 8 | BJ | | 150-199, 275-299 |
| 645 | 22 | | PA | 5-0 | 25-53-17 | S00563 | | | | 10 | C | | | D01608 | X1 | | | 050-099 |
| 645 | 22 | | PA | 6-0 | 25-53-17 | D01608 | | | | X1 | | | | S00563 | 10 | C | | 150-199, 275-299 |
| 646 | 22 | | PA | 6-0 | 25-53-17 | S00563 | | | | 1 | C | | | D01390 | X1 | | | 050-099 |
| 646 | 22 | | PA | 6-0 | 25-53-17 | D01390 | | | | X1 | | | | S00563 | 1 | C | | 150-199, 275-299 |
| 647 | 22 | | PA | 3-0 | 25-53-17 | D02462 | | | | X1 | | | | TB0112G | 31 | 2 | | ALL |
| 648 | 22 | | PA | 5-0 | 25-53-13 | D02432 | | | | X1 | | | | TB0110G | 1 | 2 | | 050-099 |
| 648 | 22 | | PA | 3-0 | 25-53-13 | D02432 | | | | 7 | | | | TB0110Z | 1 | BJ | | 150-199, 275-299 |
| 649 | 22 | | PA | 5-0 | 25-53-13 | D02432 | | | | X2 | | | | TB0110Z | 8 | BJ | | 050-099 |
| 649 | 22 | | PA | 4-0 | 25-53-13 | D02432 | | | | 3 | | | | TB0110Z | 50 | BJ | | 150-199, 275-299 |
| 650 | 22 | | PA | 5-0 | 25-53-14 | D02430 | | | | A2 | | | | TB0110G | 25 | 2 | | 050-099 |
| 650 | 22 | | PA | 2-0 | 25-53-14 | D02430 | | | | 6 | | | | TB0110G | 25 | 2 | | 150-199, 275-299 |
| 651 | 22 | | PA | 5-0 | 25-53-14 | D02430 | | | | A1 | | | | D05224J | 17 | | | 050-099 |
| 651 | 22 | | PA | 3-0 | 25-53-14 | D02430 | | | | 1 | | | | D05224J | 17 | | | 150-199, 275-299 |
| 652 | 22 | | PA | 2-0 | 25-53-14 | D02430 | | | | B2 | | | | TB0112Y | A030 | BJ | | 050-099 |
| 652 | 22 | | PA | 2-0 | 25-53-14 | D02430 | | | | 2 | | | | TB0110Z | 37 | BJ | | 150-199, 275-299 |
| 653 | 22 | | PA | 5-0 | 25-53-14 | D02430 | | | | B1 | | | | D05224J | 18 | | | 050-099 |
| 653 | 22 | | PA | 3-0 | 25-53-14 | D02430 | | | | 5 | | | | D05224J | 18 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 49

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | |
| 654 | 22 | | PA | 4-0 | 25-53-17 | D05216J | | 7 | | | TB0112G | 31 | 2 | | 050-099 |
| 654 | 22 | | PA | 5-0 | 25-53-17 | D05216J | | 7 | | | TB0112G | 31 | 2 | | 150-199, 275-299 |
| 655 | 22 | | PA | 3-0 | 25-53-17 | D01608 | | A2 | | | TB0112H | 9 | 2 | | 050-099 |
| 655 | 22 | | PA | 4-0 | 25-53-17 | D01608 | | A2 | | | TB0112Z | 8 | BJ | | 150-199, 275-299 |
| 656 | 22 | | PA | 3-0 | 25-53-17 | D01608 | | X2 | | | TB0112G | 33 | 2 | | ALL |
| 658 | 22 | | PA | 5-0 | 25-53-13 | D02430 | | X1 | | | TB0110G | 2 | 2 | | 050-099 |
| 658 | 22 | | PA | 4-0 | 25-53-13 | D02430 | | 7 | | | TB0110Z | 2 | BJ | | 150-199, 275-299 |
| 659 | 22 | | PA | 5-0 | 25-53-13 | D02430 | | X2 | | | TB0110Z | 8 | BJ | | 050-099 |
| 659 | 22 | | PA | 2-0 | 25-53-13 | D02430 | | 3 | | | TB0110Z | 50 | BJ | | 150-199, 275-299 |
| 660 | 22 | | PA | 3-0 | 25-53-14 | D02436 | | A2 | | | TB0112H | 35 | 2 | | 050-099 |
| 660 | 22 | | PA | 3-0 | 25-53-14 | D02436 | | 2 | | | TB0110Z | 27 | BJ | | 150-199, 275-299 |
| 661 | 22 | | PA | 5-0 | 25-53-14 | D02436 | | A1 | | | D05224J | 21 | | | 050-099 |
| 661 | 22 | | PA | 4-0 | 25-53-14 | D02436 | | 1 | | | D05224J | 21 | | | 150-199, 275-299 |
| 662 | 22 | | PA | 5-0 | 25-53-14 | D02436 | | B2 | | | TB0110G | 28 | 2 | | 050-099 |
| 662 | 22 | | PA | 3-0 | 25-53-14 | D02436 | | 6 | | | TB0110Z | 28 | BJ | | 150-199, 275-299 |
| 663 | 22 | | PA | 5-0 | 25-53-14 | D02436 | | B1 | | | D05224J | 22 | | | 050-099 |
| 663 | 22 | | PA | 5-0 | 25-53-14 | D02436 | | 5 | | | D05224J | 22 | | | 150-199, 275-299 |
| 664 | 22 | | PA | 5-0 | 25-53-14 | D02436 | | C2 | | | TB0110H | 43 | 2 | | 050-099 |
| 664 | 22 | | PA | 5-0 | 25-53-14 | D11704 | | 8 | | | D05224J | 40 | | | 150-199, 275-299 |
| 665 | 22 | | PA | 3-0 | 25-53-14 | D01314 | | 7 | | | TB0110H | 16 | 2 | | 050-099 |
| 665 | 22 | | PA | 5-0 | 25-53-14 | D05224J | | 44 | | | TB0110Y | A052 | BJ | | 150-199, 275-299 |
| 668 | 22 | | PA | 5-0 | 25-53-13 | D02436 | | X1 | | | TB0110G | 1 | 2 | | 050-099 |
| 668 | 22 | | PA | 2-0 | 25-53-13 | D02436 | | 7 | | | TB0112D | C030 | 2 | | 150-199, 275-299 |
| 669 | 22 | | PA | 5-0 | 25-53-13 | D02436 | | X2 | | | TB0110H | 41 | 2 | | 050-099 |
| 669 | 22 | | PA | 3-0 | 25-53-13 | D02436 | | 3 | | | TB0110H | 10 | 2 | | 150-199, 275-299 |
| 670 | 22 | | PA | 3-0 | 25-53-14 | D02434 | | A2 | | | TB0112H | 35 | 2 | | 050-099 |
| 670 | 22 | | PA | 3-0 | 25-53-14 | D02434 | | 2 | | | TB0110Z | 27 | BJ | | 150-199, 275-299 |
| 671 | 22 | | PA | 5-0 | 25-53-14 | D02434 | | A1 | | | D05224J | 24 | | | 050-099 |
| 671 | 22 | | PA | 4-0 | 25-53-14 | D02434 | | 1 | | | D05224J | 24 | | | 150-199, 275-299 |
| 672 | 22 | | PA | 5-0 | 25-53-14 | D02434 | | B2 | | | TB0110G | 28 | 2 | | 050-099 |
| 672 | 22 | | PA | 3-0 | 25-53-14 | D02434 | | 6 | | | TB0110Z | 28 | BJ | | 150-199, 275-299 |
| 673 | 22 | | PA | 5-0 | 25-53-14 | D02434 | | B1 | | | D05224J | 25 | | | 050-099 |
| 673 | 22 | | PA | 4-0 | 25-53-14 | D02434 | | 5 | | | D05224J | 25 | | | 150-199, 275-299 |
| 674 | 22 | | PA | 5-0 | 25-53-14 | D02434 | | C2 | | | D05224J | 40 | | | 050-099 |
| 675 | 22 | | PA | 2-0 | 25-53-14 | D02434 | | C3 | | | D02436 | C3 | | | 050-099 |
| 676 | 22 | | PA | 5-0 | 25-53-13 | S00563 | | 4 | C | | TB0112Z | 27 | BJ | | 050-099 |
| 677 | 22 | | PA | 2-0 | 25-53-13 | D01314 | | 3 | | | TB0110H | 52 | 2 | | 050-099 |
| 677 | 22 | | PA | 4-0 | 25-53-14 | D05224J | | 26 | | | TB0110G | 30 | 2 | | 150-199, 275-299 |
| 678 | 22 | | PA | 4-0 | 25-53-13 | D01288 | | X2 | | | TB0110H | 50 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 50

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 678 | 22 | | PA | 2-0 | 25-53-13 | D02434 | | 7 | | | | | TB0112D | C029 | 2 | | 150-199, 275-299 |
| 679 | 22 | | PA | 5-0 | 25-53-13 | D02434 | | X2 | | | | | TB0110H | 41 | 2 | | 050-099 |
| 679 | 22 | | PA | 3-0 | 25-53-13 | D02434 | | 3 | | | | | TB0110H | 10 | 2 | | 150-199, 275-299 |
| 680 | 22 | | PA | 5-0 | 25-53-14 | D02438 | | A2 | | | | | TB0110Z | 9 | BJ | | 050-099 |
| 680 | 22 | | PA | 4-0 | 25-53-14 | D02438 | | A2 | | | | | TB0112Z | 26 | BJ | | 150-199, 275-299 |
| 681 | 22 | | PA | 5-0 | 25-53-14 | D02438 | | A1 | | | | | D05224J | 20 | | | ALL |
| 682 | 22 | | PA | 5-0 | 25-53-14 | D02438 | | B2 | | | | | TB0110H | 20 | 2 | | 050-099 |
| 682 | 22 | | PA | 4-0 | 25-53-14 | D02438 | | B2 | | | | | TB0112Z | 25 | BJ | | 150-199, 275-299 |
| 683 | 22 | | PA | 5-0 | 25-53-14 | D02438 | | B1 | | | | | D05224J | 10 | | | 050-099 |
| 683 | 22 | | PA | 4-0 | 25-53-14 | D02438 | | B1 | | | | | D05224J | 10 | | | 150-199, 275-299 |
| 684 | 22 | | PA | 4-0 | 25-53-14 | D02438 | | C2 | | | | | TB0110H | 43 | 2 | | 050-099 |
| 684 | 22 | | PA | 3-0 | 25-53-14 | TB0110Y | | C052 | BJ | | | | D02456 | C2 | | | 150-199, 275-299 |
| 685 | 22 | | PA | 5-0 | 25-53-14 | D02438 | | C3 | | | | | TB0110G | 29 | 2 | | 050-099 |
| 685 | 22 | | PA | 3-0 | 25-53-14 | D02438 | | C3 | | | | | TB0110G | 30 | 2 | | 150-199, 275-299 |
| 686 | 22 | | PA | 3-0 | 25-53-14 | TB0110G | | 27 | 2 | | | | D02450 | 6 | | | 050-099 |
| 686 | 22 | | PA | 4-0 | 25-53-14 | D05224J | | 23 | | | | | TB0110G | 30 | 2 | | 150-199, 275-299 |
| 687 | 22 | | PA | 5-0 | 25-53-13 | D02434 | | X1 | | | | | TB0110G | 2 | 2 | | 050-099 |
| 689 | 22 | | PA | 5-0 | 25-53-13 | D02438 | | X2 | | | | | TB0110H | 50 | 2 | | 050-099 |
| 689 | 22 | | PA | 6-0 | 25-53-13 | S00563 | | 7 | C | | | | TB0110Z | 42 | BJ | | 150-199, 275-299 |
| 690 | 22 | | PA | 5-0 | 25-53-14 | D02442 | | 6 | | | | | TB0110G | 31 | 2 | | 050-099 |
| 690 | 22 | | PA | 4-0 | 25-53-14 | D11616 | | 6 | | | | | TB0110G | 31 | 2 | | 150-199, 275-299 |
| 691 | 22 | | PA | 5-0 | 25-53-14 | D02442 | | 1 | | | | | D05224J | 27 | | | 050-099 |
| 691 | 22 | | PA | 4-0 | 25-53-14 | D11616 | | 1 | | | | | D05224J | 27 | | | 150-199, 275-299 |
| 692 | 22 | | PA | 5-0 | 25-53-14 | D02442 | | 2 | | | | | TB0110G | 32 | 2 | | 050-099 |
| 692 | 22 | | PA | 4-0 | 25-53-14 | D11616 | | 2 | | | | | TB0110Z | 20 | BJ | | 150-199, 275-299 |
| 693 | 22 | | PA | 5-0 | 25-53-14 | D02442 | | 5 | | | | | D05224J | 28 | | | 050-099 |
| 693 | 22 | | PA | 4-0 | 25-53-14 | D11616 | | 5 | | | | | D05224J | 28 | | | 150-199, 275-299 |
| 696 | 22 | | PA | 2-0 | 25-53-14 | D01314 | | 5 | | | | | TB0110G | 27 | 2 | | 050-099 |
| 697 | 22 | | PA | 5-0 | 25-53-13 | D02444 | | 11 | | | | | TB0110Z | 8 | BJ | | 050-099 |
| 698 | 22 | | PA | 5-0 | 25-53-13 | D02442 | | 7 | | | | | TB0110G | 35 | 2 | | 050-099 |
| 698 | 22 | | PA | 4-0 | 25-53-13 | D11616 | | 7 | | | | | TB0110Z | 35 | BJ | | 150-199, 275-299 |
| 699 | 22 | | PA | 4-0 | 25-53-13 | D02442 | | 3 | | | | | TB0110D | A012 | 2 | | 050-099 |
| 699 | 22 | | PA | 4-0 | 25-53-13 | D11616 | | 3 | | | | | TB0114D | A008 | 2 | | 150-199, 275-299 |
| 700 | 22 | | PA | 5-0 | 25-53-14 | D02440 | | 6 | | | | | TB0110G | 31 | 2 | | 050-099 |
| 700 | 22 | | PA | 4-0 | 25-53-14 | D11678 | | 6 | | | | | TB0110G | 31 | 2 | | 150-199, 275-299 |
| 701 | 22 | | PA | 5-0 | 25-53-14 | D02440 | | 1 | | | | | D05224J | 31 | | | 050-099 |
| 701 | 22 | | PA | 4-0 | 25-53-14 | D11678 | | 1 | | | | | D05224J | 31 | | | 150-199, 275-299 |
| 702 | 22 | | PA | 5-0 | 25-53-14 | D02440 | | 2 | | | | | TB0110G | 32 | 2 | | 050-099 |
| 702 | 22 | | PA | 4-0 | 25-53-14 | D11678 | | 2 | | | | | TB0110Z | 20 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 51

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 703 | 22 | | PA | 5-0 | 25-53-14 | D02440 | | 5 | | | | | D05224J | 32 | | | 050-099 |
| 703 | 22 | | PA | 4-0 | 25-53-14 | D11678 | | 5 | | | | | D05224J | 32 | | | 150-199, 275-299 |
| 704 | 22 | | PA | 3-0 | 25-53-17 | D02464 | | X1 | | | | | TB0112G | 32 | 2 | | ALL |
| 705 | 22 | | PA | 6-0 | 25-53-17 | TB0112G | | 32 | 2 | | | | S00563 | 2 | C | | ALL |
| 706 | 22 | | PA | 3-0 | 25-53-14 | D01288 | | B1 | | | | | TB0112Y | C029 | BJ | | 050-099 |
| 707 | 22 | | PA | 2-0 | 25-53-14 | TB0112Y | | A029 | BJ | | | | D02456 | D1 | | | 050-099 |
| 708 | 22 | | PA | 5-0 | 25-53-13 | D02440 | | 7 | | | | | TB0110G | 36 | 2 | | 050-099 |
| 708 | 22 | | PA | 4-0 | 25-53-13 | D11678 | | 7 | | | | | TB0110Z | 36 | BJ | | 150-199, 275-299 |
| 709 | 22 | | PA | 4-0 | 25-53-13 | D02440 | | 3 | | | | | TB0114D | A | 2 | | 050-099 |
| 709 | 22 | | PA | 4-0 | 25-53-13 | D11678 | | 3 | | | | | TB0114D | A007 | 2 | | 150-199, 275-299 |
| 710 | 22 | | PA | 5-0 | 25-53-14 | D02496 | | 6 | | | | | TB0110H | 20 | 2 | | 050-099 |
| 710 | 22 | | PA | 4-0 | 25-53-14 | D13048 | | 6 | | | | | TB0112Y | C011 | BJ | | 150-199, 275-299 |
| 711 | 22 | | PA | 5-0 | 25-53-14 | D02496 | | 1 | | | | | D05224J | 34 | | | 050-099 |
| 711 | 22 | | PA | 5-0 | 25-53-14 | D13048 | | 1 | | | | | D05224J | 34 | | | 150-199, 275-299 |
| 712 | 22 | | PA | 5-0 | 25-53-14 | D02496 | | 2 | | | | | TB0110G | 33 | 2 | | 050-099 |
| 712 | 22 | | PA | 4-0 | 25-53-14 | D13048 | | 2 | | | | | TB0110Z | 33 | BJ | | 150-199, 275-299 |
| 713 | 22 | | PA | 5-0 | 25-53-14 | D02496 | | 5 | | | | | D05224J | 35 | | | 050-099 |
| 713 | 22 | | PA | 5-0 | 25-53-14 | D13048 | | 5 | | | | | D05224J | 35 | | | 150-199, 275-299 |
| 714 | 22 | | PA | 5-0 | 25-53-14 | D01288 | | A2 | | | | | TB0110H | 14 | 2 | | 050-099 |
| 715 | 22 | | PA | 3-0 | 25-53-14 | D01288 | | B2 | | | | | TB0112Y | C030 | BJ | | 050-099 |
| 716 | 22 | | PA | 2-0 | 25-53-14 | D01288 | | C2 | | | | | TB0112Y | C012 | BJ | | 050-099 |
| 718 | 22 | | PA | 5-0 | 25-53-13 | D02496 | | 7 | | | | | TB0110G | 35 | 2 | | 050-099 |
| 718 | 22 | | PA | 4-0 | 25-53-13 | D13048 | | 7 | | | | | TB0110Z | 35 | BJ | | 150-199, 275-299 |
| 719 | 22 | | PA | 4-0 | 25-53-13 | D02496 | | 3 | | | | | TB0110D | A034 | 2 | | 050-099 |
| 719 | 22 | | PA | 5-0 | 25-53-13 | D13048 | | 3 | | | | | TB0114D | A011 | 2 | | 150-199, 275-299 |
| 720 | 22 | | PA | 5-0 | 25-53-14 | D02494 | | 6 | | | | | TB0110G | 31 | 2 | | 050-099 |
| 720 | 22 | | PA | 1-0 | 25-53-14 | D02488 | | 2 | | | | | TB0110Z | 18 | BJ | | 150-199, 275-299 |
| 721 | 22 | | PA | 5-0 | 25-53-14 | D02494 | | 1 | | | | | D05224J | 37 | | | 050-099 |
| 721 | 22 | | PA | 5-0 | 25-53-14 | D13050 | | 1 | | | | | D05224J | 37 | | | 150-199, 275-299 |
| 722 | 22 | | PA | 5-0 | 25-53-14 | D02494 | | 2 | | | | | TB0110G | 33 | 2 | | 050-099 |
| 722 | 22 | | PA | 4-0 | 25-53-14 | D13050 | | 2 | | | | | TB0110Z | 33 | BJ | | 150-199, 275-299 |
| 723 | 22 | | PA | 5-0 | 25-53-14 | D02494 | | 5 | | | | | D05224J | 38 | | | 050-099 |
| 723 | 22 | | PA | 5-0 | 25-53-14 | D13050 | | 5 | | | | | D05224J | 38 | | | 150-199, 275-299 |
| 728 | 22 | | PA | 5-0 | 25-53-13 | D02494 | | 7 | | | | | TB0110G | 36 | 2 | | 050-099 |
| 728 | 22 | | PA | 4-0 | 25-53-13 | D13050 | | 7 | | | | | TB0110Z | 36 | BJ | | 150-199, 275-299 |
| 729 | 22 | | PA | 4-0 | 25-53-13 | D02494 | | 3 | | | | | TB0114D | A | 2 | | 050-099 |
| 729 | 22 | | PA | 5-0 | 25-53-13 | D13050 | | 3 | | | | | TB0114D | A012 | 2 | | 150-199, 275-299 |
| 730 | 22 | | PA | 2-0 | 25-53-14 | TB0110H | | 14 | 2 | | | | TB0110H | 16 | 2 | | 050-099 |
| 730 | 22 | | PA | 1-0 | 25-53-14 | TB0110Z | | 14 | BJ | | | | TB0110Z | 15 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 52

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | |
| 731 | 22 | | PA | 2-0 | 25-53-14 | TB0110G | 3 | 2 | | TB0110H | 20 | 2 | | 050-099 | | |
| 736 | 22 | | PA | 2-0 | 25-53-14 | D02472 | 2 | | | TB0110G | 3 | 2 | | 050-099 | | |
| 736 | 22 | | PA | 1-0 | 25-53-14 | D02472 | 2 | | | TB0110Z | 18 | BJ | | 150-199, 275-299 | | |
| 737 | 22 | | PA | 2-0 | 25-53-14 | D02472 | 5 | | | TB0110G | 22 | 2 | | ALL | | |
| 738 | 22 | | PA | 2-0 | 25-53-14 | D02472 | 7 | | | TB0110G | 24 | 2 | | 050-099 | | |
| 738 | 22 | | PA | 2-0 | 25-53-14 | D02472 | 7 | | | D02476 | 1 | | | 150-199, 275-299 | | |
| 739 | 22 | | PA | 7-0 | 25-53-13 | D02472 | 3 | | | S00383 | 5 | C | * | 050-099 | | |
| 739 | 22 | | PA | 4-0 | 25-53-13 | D02472 | 3 | | | TB0114D | C004 | 2 | | 150-199, 275-299 | | |
| 746 | 22 | | PA | 2-0 | 25-53-14 | D02476 | 2 | | | TB0110H | 18 | 2 | | 050-099 | | |
| 746 | 22 | | PA | 1-0 | 25-53-14 | D02476 | 2 | | | TB0110Z | 18 | BJ | | 150-199, 275-299 | | |
| 747 | 22 | | PA | 2-0 | 25-53-14 | D02476 | 5 | | | TB0110G | 24 | 2 | | ALL | | |
| 748 | 22 | | PA | 2-0 | 25-53-14 | D02476 | 7 | | | TB0110H | 18 | 2 | | 050-099 | | |
| 748 | 22 | | PA | 2-0 | 25-53-14 | D02476 | 7 | | | TB0110Z | 7 | BJ | | 150-199, 275-299 | | |
| 749 | 22 | | PA | 2-0 | 25-53-13 | D02476 | 3 | | | TB0110Z | 21 | BJ | | 150-199, 275-299 | | |
| 750 | 22 | | PA | 2-0 | 25-53-14 | D02478 | 2 | | | TB0110H | 14 | 2 | | 050-099 | | |
| 750 | 22 | | PA | 1-0 | 25-53-14 | D02478 | 2 | | | TB0110Z | 14 | BJ | | 150-199, 275-299 | | |
| 751 | 22 | | PA | 2-0 | 25-53-14 | D02478 | 5 | | | TB0110G | 25 | 2 | | 050-099 | | |
| 751 | 22 | | PA | 1-0 | 25-53-14 | D02478 | 5 | | | TB0110G | 25 | 2 | | 150-199, 275-299 | | |
| 752 | 22 | | PA | 2-0 | 25-53-14 | D02478 | 7 | | | TB0110H | 14 | 2 | | 050-099 | | |
| 752 | 22 | | PA | 1-0 | 25-53-14 | D02478 | 7 | | | TB0110Z | 14 | BJ | | 150-199, 275-299 | | |
| 753 | 22 | | PA | 2-0 | 25-53-13 | D02478 | 3 | | | TB0110Z | 8 | BJ | | 050-099 | | |
| 753 | 22 | | PA | 2-0 | 25-53-13 | D02478 | 3 | | | TB0110Z | 50 | BJ | | 150-199, 275-299 | | |
| 754 | 22 | | PA | 4-0 | 25-53-16 | TB0110G | 26 | 2 | | TB0112D | A022 | 2 | | 150-199, 275-299 | | |
| 756 | 22 | | PA | 2-0 | 25-53-14 | D01518 | 2 | | | TB0110Z | 6 | BJ | | 150-199, 275-299 | | |
| 757 | 22 | | PA | 2-0 | 25-53-14 | D01518 | 5 | | | TB0110Z | 37 | BJ | | 150-199, 275-299 | | |
| 758 | 22 | | PA | 3-0 | 25-53-14 | D01518 | 7 | | | TB0110Z | 6 | BJ | | 150-199, 275-299 | | |
| 759 | 22 | | PA | 2-0 | 25-53-13 | D01518 | 3 | | | TB0110Z | 50 | BJ | | 150-199, 275-299 | | |
| 760 | 22 | | PA | 2-0 | 25-53-14 | D02488 | 2 | | | TB0110Z | 9 | BJ | | 050-099 | | |
| 760 | 22 | | PA | 1-0 | 25-53-14 | D02484 | 2 | | | TB0110Z | 6 | BJ | | 150-199, 275-299 | | |
| 761 | 22 | | PA | 3-0 | 25-53-14 | D02488 | 5 | | | TB0112H | 35 | 2 | | 050-099 | | |
| 761 | 22 | | PA | 4-0 | 25-53-14 | D11704 | 5 | | | TB0110Z | 27 | BJ | | 150-199, 275-299 | | |
| 762 | 22 | | PA | 2-0 | 25-53-14 | D02488 | 7 | | | TB0110Z | 9 | BJ | | 050-099 | | |
| 762 | 22 | | PA | 4-0 | 25-53-14 | D11704 | 7 | | | TB0110Z | 19 | BJ | | 150-199, 275-299 | | |
| 763 | 22 | | PA | 2-0 | 25-53-13 | D02488 | 3 | | | TB0110H | 41 | 2 | | 050-099 | | |
| 763 | 22 | | PA | 3-0 | 25-53-13 | D11704 | 3 | | | TB0110H | 10 | 2 | | 150-199, 275-299 | | |
| 766 | 22 | | PA | 2-0 | 25-53-14 | D02484 | 2 | | | TB0110H | 20 | 2 | | 050-099 | | |
| 766 | 22 | | PA | 3-0 | 25-53-14 | D11704 | 2 | | | TB0110Z | 19 | BJ | | 150-199, 275-299 | | |
| 767 | 22 | | PA | 2-0 | 25-53-14 | D02484 | 5 | | | TB0110G | 28 | 2 | | 050-099 | | |
| 767 | 22 | | PA | 2-0 | 25-53-14 | D02484 | 5 | | | TB0110Z | 28 | BJ | | 150-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 53

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 768 | 22 | | PA | 2-0 | 25-53-14 | D02484 | | 7 | | | | | TB0110H | 20 | 2 | | 050-099 |
| 768 | 22 | | PA | 1-0 | 25-53-14 | D02484 | | 7 | | | | | TB0110Z | 6 | BJ | | 150-199, 275-299 |
| 769 | 22 | | PA | 2-0 | 25-53-13 | D02484 | | 3 | | | | | TB0110H | 41 | 2 | | 050-099 |
| 769 | 22 | | PA | 1-0 | 25-53-13 | D02484 | | 3 | | | | | TB0110H | 10 | 2 | | 150-199, 275-299 |
| 774 | 22 | | PA | 4-0 | 25-53-13 | D02476 | | 3 | | | | | TB0110H | 52 | 2 | | 050-099 |
| 775 | 22 | | PA | 4-0 | 25-53-14 | D01314 | | 2 | | | | | TB0110H | 16 | 2 | | 050-099 |
| 776 | 22 | | PA | 5-0 | 25-53-13 | TB0110G | | 30 | 2 | | | | D01288 | X1 | | | 050-099 |
| 777 | 22 | | PA | 3-0 | 25-53-13 | TB0110H | | 52 | 2 | | | | TB0110G | 7 | 2 | | 050-099 |
| 778 | 22 | | PA | 4-0 | 25-53-13 | D01284 | | X2 | | | | | TB0114H | 5 | 2 | | 050-099 |
| 779 | 22 | | PA | 4-0 | 25-53-13 | D05216J | | 21 | | | | | TB0112Z | 27 | BJ | | 050-099 |
| 780 | 22 | | PA | 5-0 | 25-53-13 | L00436 | | =P | \$ | | | | TB0112Z | 27 | BJ | | 050-099 |
| 780 | 22 | | PA | 1-0 | 25-53-14 | D02488 | | 6 | | | | | TB0110Z | 18 | BJ | | 150-199, 275-299 |
| 781 | 22 | | PA | 1-0 | 25-53-14 | D02488 | | 1 | | | | | TB0110G | 31 | 2 | | 150-199, 275-299 |
| 782 | 22 | | PA | 6-0 | 25-53-13 | L00436 | | =G | \$ | | | | TB0114H | 5 | 2 | | 050-099 |
| 782 | 22 | | PA | 1-0 | 25-53-14 | D02488 | | 7 | | | | | TB0110Z | 18 | BJ | | 150-199, 275-299 |
| 783 | 22 | | PA | 2-0 | 25-53-13 | D02488 | | 3 | | | | | TB0110Z | 51 | BJ | | 150-199, 275-299 |
| 786 | 22 | | PA | 2-0 | 25-53-14 | D02490 | | 2 | | | | | TB0110H | 16 | 2 | | 050-099 |
| 786 | 22 | | PA | 1-0 | 25-53-14 | D02490 | | 2 | | | | | TB0110Z | 15 | BJ | | 150-199, 275-299 |
| 787 | 22 | | PA | 2-0 | 25-53-14 | D02490 | | 5 | | | | | TB0110G | 32 | 2 | | 050-099 |
| 787 | 22 | | PA | 1-0 | 25-53-14 | D02490 | | 5 | | | | | TB0110Z | 20 | BJ | | 150-199, 275-299 |
| 788 | 22 | | PA | 3-0 | 25-53-14 | D02490 | | 7 | | | | | TB0112H | 35 | 2 | | 050-099 |
| 788 | 22 | | PA | 2-0 | 25-53-14 | D02490 | | 7 | | | | | TB0110Z | 27 | BJ | | 150-199, 275-299 |
| 789 | 22 | | PA | 2-0 | 25-53-13 | D02490 | | 3 | | | | | TB0110D | C012 | 2 | | 050-099 |
| 789 | 22 | | PA | 2-0 | 25-53-13 | D02490 | | 3 | | | | | TB0110Z | 51 | BJ | | 150-199, 275-299 |
| 792 | 22 | | PA | 4-0 | 25-53-14 | D11632 | | 4 | | | | | D11624 | 1 | | | 050-099 |
| 792 | 22 | | PA | 5-0 | 25-53-14 | D11624 | | 1 | | | | | D11632 | 4 | | | 150-199, 275-299 |
| 793 | 22 | | PA | 5-0 | 25-53-14 | D11624 | | 13 | | | | | TB0110H | 43 | 2 | | 050-099 |
| 793 | 22 | | PA | 4-0 | 25-53-14 | D11624 | | 13 | | | | | TB0110Z | 43 | BJ | | 150-199, 275-299 |
| 795 | 22 | | PA | 5-0 | 25-53-16 | TB0306Y | | C002 | BJ | | | | TB0112D | A022 | 2 | | 050-099 |
| 796 | 22 | | PA | 2-0 | 25-53-14 | D02492 | | 2 | | | | | TB0110H | 16 | 2 | | 050-099 |
| 796 | 22 | | PA | 1-0 | 25-53-14 | D02492 | | 2 | | | | | TB0110Z | 15 | BJ | | 150-199, 275-299 |
| 797 | 22 | | PA | 2-0 | 25-53-14 | D02492 | | 5 | | | | | TB0110G | 33 | 2 | | 050-099 |
| 797 | 22 | | PA | 2-0 | 25-53-14 | D02492 | | 5 | | | | | TB0110Z | 33 | BJ | | 150-199, 275-299 |
| 798 | 22 | | PA | 3-0 | 25-53-14 | D02492 | | 7 | | | | | TB0112H | 35 | 2 | | 050-099 |
| 798 | 22 | | PA | 2-0 | 25-53-14 | D02492 | | 7 | | | | | TB0110Z | 27 | BJ | | 150-199, 275-299 |
| 799 | 22 | | PA | 2-0 | 25-53-13 | D02492 | | 3 | | | | | TB0110D | C034 | 2 | | 050-099 |
| 799 | 22 | | PA | 2-0 | 25-53-13 | D02492 | | 3 | | | | | TB0110Z | 51 | BJ | | 150-199, 275-299 |
| 800 | 22 | | PA | 4-0 | 25-53-14 | D05216J | | 14 | | | | | TB0112Y | A013 | BJ | | 050-099 |
| 801 | 24 | | PK | 3-0 | 52-34-12 | D05886J | | 1 | | | | | S00411 | 12 | C | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1060
Page 54
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 802 | 24 | | PK | 4-0 | 52-34-12 | D05886J | | 2 | | | | | TB0110G | 49 | 2 | | 050-099 |
| 802 | 24 | | PK | 3-0 | 52-34-12 | D05886J | | 2 | | | | | TB0110G | 49 | 2 | | 150-199, 275-299 |
| 803 | 24 | | PK | 4-0 | 52-34-12 | D05886J | | 3 | | | | | TB0110G | 48 | 2 | | 050-099 |
| 803 | 24 | | PK | 3-0 | 52-34-12 | D05886J | | 3 | | | | | TB0110G | 48 | 2 | | 150-199, 275-299 |
| 804 | 24 | | PK | 3-0 | 52-34-12 | D05886J | | 4 | | | | | TB0114G | 7 | 2 | | 050-099 |
| 804 | 24 | | PK | 5-0 | 52-34-12 | D05886J | | 4 | | | | | TB0110G | 5 | 2 | | 150-199, 275-299 |
| 805 | 22 | | PA | 5-0 | 25-53-14 | D01284 | | | D1 | | | | D02476 | 1 | | | 050-099 |
| 807 | 22 | | PA | 4-0 | 25-53-14 | D01284 | | | D2 | | | | TB0110G | 22 | 2 | | 050-099 |
| 807 | 24 | | PK | 2-0 | 52-34-12 | D05886J | | 7 | | | | | TB0114D | A001 | 2 | | 150-199, 275-299 |
| 808 | 22 | | PA | 6-0 | 25-53-13 | S00563 | | 9 | C | | | | D02444 | 10 | | | 050-099 |
| 809 | 22 | | PA | 6-0 | 25-53-13 | S00563 | | 8 | C | | | | TB0110H | 41 | 2 | | 050-099 |
| 810 | 22 | | PA | 6-0 | 25-53-13 | S00563 | | 7 | C | | | | TB0110Z | 8 | BJ | | 050-099 |
| 811 | 22 | | PA | 2-0 | 25-53-13 | D01284 | | | C1 | | | | D02438 | X1 | | | 050-099 |
| 813 | 22 | | PA | 2-0 | 25-53-13 | L00619 | | | =G | \$ | * | | L00145 | =G | \$ | * | 050-099 |
| 814 | 22 | | PA | 3-0 | 25-53-13 | S00384 | | 6 | C | | | | L00145 | =P | \$ | | 050-099 |
| 814 | 24 | | PK | 5-0 | 52-34-12 | S00411 | | 8 | C | | | | TB0110G | 5 | 2 | | 150-199, 275-299 |
| 815 | 22 | | PA | 5-0 | 25-53-14 | D05224J | | 16 | | | | | TB0112G | 11 | 2 | | 050-099 |
| 816 | 22 | | PA | 2-0 | 25-53-13 | S00384 | | 10 | C | | | | S00384 | 9 | C | | 050-099 |
| 817 | 24 | | PK | 3-0 | 52-34-12 | D05886J | | 7 | | | | | R00035 | A | 2 | | 050-099 |
| 818 | 24 | | PK | 4-0 | 52-34-12 | S00411 | | 8 | C | | | | TB0114G | 7 | 2 | | 050-099 |
| 819 | 24 | | PK | 4-0 | 52-34-12 | S00411 | | 9 | C | | | | TB0110G | 48 | 2 | | 050-099 |
| 819 | 24 | | PK | 3-0 | 52-34-12 | S00411 | | 9 | C | | | | TB0110G | 48 | 2 | | 150-199, 275-299 |
| 820 | 24 | | PK | 2-0 | 52-34-12 | S00411 | | 7 | C | | | | S00411 | 11 | C | | 050-099 |
| 820 | 24 | | PK | 1-0 | 52-34-12 | S00411 | | 7 | C | | | | S00411 | 11 | C | | 150-199, 275-299 |
| 821 | 24 | | PK | 4-0 | 52-34-12 | S00411 | | 10 | C | | | | TB0110G | 49 | 2 | | 050-099 |
| 821 | 24 | | PK | 3-0 | 52-34-12 | S00411 | | 10 | C | | | | TB0110G | 49 | 2 | | 150-199, 275-299 |
| 823 | 22 | | PA | 5-0 | 25-53-14 | D02430 | | | C2 | | | | TB0110H | 43 | 2 | | 050-099 |
| 824 | 24 | | PK | 2-0 | 52-34-12 | D02506 | | | X1 | | | | TB0110G | 48 | 2 | | ALL |
| 825 | 24 | | PK | 2-0 | 52-34-12 | D02508 | | | X1 | | | | TB0110G | 49 | 2 | | 050-099 |
| 825 | 24 | | PK | 1-0 | 52-34-12 | D02508 | | | X1 | | | | TB0110G | 49 | 2 | | 150-199, 275-299 |
| 828 | 24 | | PK | 2-0 | 52-34-12 | D02502 | | | X1 | | | | TB0110G | 48 | 2 | | ALL |
| 829 | 24 | | PK | 2-0 | 52-34-12 | D02504 | | | X1 | | | | TB0110G | 49 | 2 | | 050-099 |
| 829 | 24 | | PK | 1-0 | 52-34-12 | D02504 | | | X1 | | | | TB0110G | 49 | 2 | | 150-199, 275-299 |
| 830 | 20 | | PA | 3-0 | 26-16-21 | D02520 | | 6 | | | | | TB0112G | 19 | 2 | | 050-099 |
| 830 | 20 | | PA | 4-0 | 26-16-21 | D02520 | | 6 | | | | | TB0112G | 19 | 2 | | 150-199, 275-299 |
| 831 | 20 | | PA | 3-0 | 26-16-21 | D02520 | | 12 | | | | | TB0112H | 23 | 2 | | 050-099 |
| 831 | 20 | | PA | 4-0 | 26-16-21 | D02520 | | 12 | | | | | TB0112H | 23 | 2 | | 150-199, 275-299 |
| 832 | 20 | | PA | 3-0 | 26-16-21 | D02520 | | 1 | | | | | TB0112H | 15 | 2 | | 050-099 |
| 832 | 20 | | PA | 4-0 | 26-16-21 | D02520 | | 1 | | | | | TB0112H | 15 | 2 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 55

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | |
| 833 | 20 | PA | | | 3-0 | 26-16-21 | D02520 | | 2 | | TB0112G | 19 | 2 | | 050-099 |
| 833 | 20 | PA | | | 4-0 | 26-16-21 | D02520 | | 2 | | TB0112G | 19 | 2 | | 150-199, 275-299 |
| 834 | 20 | PA | | | 5-0 | 26-16-21 | D02520 | | 7 | | D05214J | 4 | | | 050-099 |
| 834 | 20 | PA | | | 4-0 | 26-16-21 | D02520 | | 7 | | D05214J | 4 | | | 150-199, 275-299 |
| 835 | 20 | PA | | | 3-0 | 26-16-21 | D02520 | | 8 | | TB0112H | 23 | 2 | | 050-099 |
| 835 | 20 | PA | | | 4-0 | 26-16-21 | D02520 | | 8 | | TB0112H | 23 | 2 | | 150-199, 275-299 |
| 838 | 20 | PA | | | 4-0 | 26-16-21 | D05214J | | 8 | | TB0112H | 15 | 2 | | ALL |
| 839 | 20 | PA | | | 4-0 | 26-16-21 | D05214J | | 9 | | TB0112H | 23 | 2 | | ALL |
| 840 | 20 | PA | | | 3-0 | 26-16-21 | D02524 | | 7 | | TB0112H | 15 | 2 | | ALL |
| 841 | 20 | PA | | | 4-0 | 26-16-21 | D02524 | | 3 | | D05214J | 3 | | | 050-099 |
| 841 | 20 | PA | | | 3-0 | 26-16-21 | D02524 | | 3 | | D05214J | 3 | | | 150-199, 275-299 |
| 844 | 20 | PA | | | 3-0 | 26-16-21 | D02524 | | 6 | | TB0112H | 15 | 2 | | ALL |
| 845 | 20 | PA | | | 3-0 | 26-16-21 | D02524 | | 1 | | TB0112G | 19 | 2 | | ALL |
| 847 | 22 | PA | | | 4-0 | 25-53-14 | D05216J | | 15 | | TB0110G | 26 | 2 | | 050-099 |
| 848 | 22 | PA | | | 4-0 | 25-53-13 | D02444 | | 6 | | TB0110G | 13 | 2 | | 050-099 |
| 848 | 22 | PA | | | 3-0 | 25-53-13 | D02444 | | 6 | | TB0110Y | A053 | BJ | | 150-199, 275-299 |
| 849 | 22 | PA | | | 2-0 | 25-53-14 | D02456 | | C2 | | TB0112Y | C012 | BJ | | 050-099 |
| 850 | 20 | PA | | | 3-0 | 26-16-21 | D02522 | | 6 | | TB0112G | 21 | 2 | | 050-099 |
| 850 | 20 | PA | | | 4-0 | 26-16-21 | D02522 | | 6 | | TB0112G | 21 | 2 | | 150-199, 275-299 |
| 851 | 20 | PA | | | 3-0 | 26-16-21 | D02522 | | 12 | | TB0112H | 23 | 2 | | 050-099 |
| 851 | 20 | PA | | | 4-0 | 26-16-21 | D02522 | | 12 | | TB0112H | 23 | 2 | | 150-199, 275-299 |
| 852 | 20 | PA | | | 3-0 | 26-16-21 | D02522 | | 1 | | TB0112H | 15 | 2 | | 050-099 |
| 852 | 20 | PA | | | 4-0 | 26-16-21 | D02522 | | 1 | | TB0112H | 15 | 2 | | 150-199, 275-299 |
| 853 | 20 | PA | | | 3-0 | 26-16-21 | D02522 | | 2 | | TB0112G | 21 | 2 | | 050-099 |
| 853 | 20 | PA | | | 4-0 | 26-16-21 | D02522 | | 2 | | TB0112G | 21 | 2 | | 150-199, 275-299 |
| 854 | 20 | PA | | | 5-0 | 26-16-21 | D02522 | | 7 | | D05214J | 14 | | | 050-099 |
| 854 | 20 | PA | | | 4-0 | 26-16-21 | D02522 | | 7 | | D05214J | 14 | | | 150-199, 275-299 |
| 855 | 20 | PA | | | 3-0 | 26-16-21 | D02522 | | 8 | | TB0112H | 23 | 2 | | 050-099 |
| 855 | 20 | PA | | | 4-0 | 26-16-21 | D02522 | | 8 | | TB0112H | 23 | 2 | | 150-199, 275-299 |
| 857 | 22 | PA | | | 4-0 | 25-53-16 | TB0112Z | | 26 | BJ | TB0114H | 5 | 2 | | 050-099 |
| 858 | 22 | PA | | | 4-0 | 25-53-14 | D05224J | | 30 | | TB0306Y | C004 | BJ | | 050-099 |
| 860 | 20 | PA | | | 3-0 | 26-16-21 | D02526 | | 7 | | TB0112H | 15 | 2 | | ALL |
| 861 | 20 | PA | | | 4-0 | 26-16-21 | D02526 | | 3 | | D05214J | 13 | | | 050-099 |
| 861 | 20 | PA | | | 3-0 | 26-16-21 | D02526 | | 3 | | D05214J | 13 | | | 150-199, 275-299 |
| 864 | 20 | PA | | | 3-0 | 26-16-21 | D02526 | | 6 | | TB0112H | 15 | 2 | | ALL |
| 865 | 20 | PA | | | 3-0 | 26-16-21 | D02526 | | 1 | | TB0112G | 21 | 2 | | ALL |
| 868 | 20 | PA | | | 4-0 | 25-53-11 | C00076 | | 2 | D | TB0112G | 34 | 2 | | 050-099 |
| 868 | 20 | PA | | | 5-0 | 25-53-11 | C00076 | | 2 | D | TB0112G | 28 | 2 | | 150-199, 275-299 |
| 869 | 20 | PA | | | 6-0 | 25-53-11 | C00077 | | 2 | D | TB0112G | 34 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 56

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | | | |
| 869 | 20 | | PA | 5-0 | 25-53-11 | C00077 | | 2 | D | | | | TB0112G | 28 | 2 | | 150-199, 275-299 |
| 870 | 22 | | PA | 6-0 | 25-53-14 | C00077 | | 1 | D | | | | TB0110G | 23 | 2 | | 050-099 |
| 870 | 22 | | PA | 5-0 | 25-53-14 | C00077 | | 1 | D | | | | TB0110G | 23 | 2 | | 150-199, 275-299 |
| 871 | 22 | | PA | 5-0 | 25-53-14 | D01684 | | A2 | | | | | TB0110G | 23 | 2 | | 050-099 |
| 871 | 22 | | PA | 3-0 | 25-53-14 | D01684 | | A2 | | | | | TB0110G | 23 | 2 | | 150-199, 275-299 |
| 872 | 22 | | PA | 5-0 | 25-53-14 | D01684 | | A1 | | | | | TB0110H | 14 | 2 | | 050-099 |
| 872 | 22 | | PA | 3-0 | 25-53-14 | D01684 | | B1 | | | | | TB0110Z | 14 | BJ | | 150-199, 275-299 |
| 873 | 22 | | PA | 5-0 | 25-53-14 | D01684 | | X2 | | | | | TB0110H | 50 | 2 | | 050-099 |
| 873 | 22 | | PA | 3-0 | 25-53-14 | D01684 | | X2 | | | | | TB0110Z | 41 | BJ | | 150-199, 275-299 |
| 874 | 22 | | PA | 5-0 | 25-53-14 | D01686 | | A2 | | | | | TB0110G | 23 | 2 | | 050-099 |
| 874 | 22 | | PA | 3-0 | 25-53-14 | D01686 | | A2 | | | | | TB0110G | 23 | 2 | | 150-199, 275-299 |
| 875 | 22 | | PA | 5-0 | 25-53-14 | D01686 | | A1 | | | | | TB0110G | 3 | 2 | | 050-099 |
| 875 | 22 | | PA | 3-0 | 25-53-14 | D01686 | | B1 | | | | | TB0110Z | 18 | BJ | | 150-199, 275-299 |
| 876 | 22 | | PA | 5-0 | 25-53-14 | D01686 | | X2 | | | | | TB0110H | 50 | 2 | | 050-099 |
| 876 | 22 | | PA | 3-0 | 25-53-14 | D01686 | | X2 | | | | | TB0110Z | 41 | BJ | | 150-199, 275-299 |
| 877 | 22 | | PA | 4-0 | 25-53-14 | TB0112D | | A004 | 2 | | | | TB0110G | 26 | 2 | | 150-199, 275-299 |
| 878 | 22 | | PA | 4-0 | 25-53-13 | TB0110Z | | 2 | BJ | | | | TB0112D | A029 | 2 | | 150-199, 275-299 |
| 879 | 22 | | PA | 4-0 | 25-53-13 | TB0110Z | | 1 | BJ | | | | TB0112D | A030 | 2 | | 150-199, 275-299 |
| 880 | 22 | | PA | 5-0 | 25-53-17 | S00563 | | 11 | C | | | | TB0112G | 31 | 2 | | 050-099 |
| 880 | 22 | | PA | 6-0 | 25-53-17 | TB0112G | | 31 | 2 | | | | S00563 | 11 | C | | 150-199, 275-299 |
| 883 | 22 | | PA | 6-0 | 25-53-15 | TB0114H | | 3 | 2 | | | | S00387 | 3 | C | | 050-099 |
| 884 | 22 | | PA | 6-0 | 25-53-15 | TB0114H | | 3 | 2 | | | | S00388 | 3 | C | | 050-099 |
| 885 | 22 | | PA | 4-0 | 25-53-13 | TB0110G | | 30 | 2 | | | | D01284 | C2 | | | 050-099 |
| 886 | 22 | | PA | 2-0 | 25-53-14 | D02430 | | C3 | | | | | D02432 | C3 | | | 050-099 |
| 887 | 22 | | PA | 6-0 | 25-53-16 | TB0306Y | | C002 | BJ | | | | TB0112D | A018 | 2 | | 050-099 |
| 888 | 20 | | PA | 3-0 | 25-53-17 | TB0112G | | 33 | 2 | | | | TB0112H | 5 | 2 | | 050-099 |
| 888 | 22 | | PA | 1-0 | 25-53-17 | TB0112G | | 27 | 2 | | | | TB0112G | 33 | 2 | | 150-199, 275-299 |
| 889 | 22 | | PA | 2-0 | 25-53-14 | TB0110H | | 20 | 2 | | | | D02476 | 6 | | | 050-099 |
| 890 | 20 | | PA | 5-0 | 25-53-11 | D02466 | | 3 | | | | | TB0114D | A | 2 | | 050-099 |
| 891 | 22 | | PA | 3-0 | 25-53-13 | S00563 | | 9 | C | | | | S00384 | 9 | C | | 050-099 |
| 892 | 22 | | PA | 3-0 | 25-53-13 | D01518 | | 3 | | | | | TB0110Z | 8 | BJ | | 050-099 |
| 893 | 22 | | PA | 4-0 | 25-53-11 | C00076 | | 1 | D | | | | TB0114H | 3 | 2 | | 050-099 |
| 893 | 22 | | PA | 5-0 | 25-53-11 | TB0112Z | | 5 | BJ | | | | C00076 | 1 | D | * | 150-199, 275-299 |
| 894 | 22 | | PA | 3-0 | 25-53-14 | TB0110H | | 20 | 2 | | | | TB0112Y | C030 | BJ | | 050-099 |
| 895 | 22 | | PA | 2-0 | 25-53-14 | D11632 | | 7 | | | | | TB0110D | C011 | 2 | | 050-099 |
| 895 | 22 | | PA | 5-0 | 25-53-14 | TB0114D | | C010 | 2 | | | | D11632 | 7 | | | 150-199, 275-299 |
| 896 | 22 | | PA | 4-0 | 25-53-14 | TB0110D | | A011 | 2 | | | | TB0112Y | A030 | BJ | | 050-099 |
| 896 | 22 | | PA | 5-0 | 25-53-14 | TB0114D | | A010 | 2 | | | | TB0110Z | 37 | BJ | | 150-199, 275-299 |
| 897 | 22 | | PA | 2-0 | 25-53-14 | TB0110D | | C010 | 2 | | | | TB0110D | C011 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 57

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|-------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1066 | 286T1066 | | | FWD CARGO LOADING ACCESSORY PANEL P35 (continued) | | | | | | | | | | | |
| 897 | 22 | | PA | | 1-0 | 25-53-14 | TB0114D | C009 | 2 | | TB0114D | C010 | 2 | | 150-199, 275-299 |
| 898 | 22 | | PA | | 4-0 | 25-53-14 | TB0110D | A010 | 2 | | TB0112H | 35 | 2 | | 050-099 |
| 898 | 22 | | PA | | 5-0 | 25-53-14 | TB0114D | A009 | 2 | | TB0110Z | 27 | BJ | | 150-199, 275-299 |
| 899 | 22 | | PA | | 2-0 | 25-53-11 | S00563 | | 5 | C | S00384 | 2 | C | * | 050-099 |
| A-A | | | | | 0-0 | 23-41-11 | D08547 | RED | | | SM00001 | | S | | ALL |
| A-B | | | | | 0-0 | 23-41-11 | D08547 | BLU | | | SM00002 | | S | | ALL |
| A-C | | | | | 0-0 | 23-41-11 | D08547 | BLK | | | SM00003 | | S | | ALL |
| PB1 | | | | | 0-0 | 99-99-99 | D02502 | G2 | | | D02502 | G3 | | | ALL |
| PC1 | | | | | 0-0 | 99-99-99 | D02504 | G2 | | | D02504 | G3 | | | ALL |
| PD1 | | | | | 0-0 | 99-99-99 | D02528 | G2 | | | D02528 | G3 | | | ALL |
| W1067 | 286T1067 | | | E2-2 SHELF,L DME COAX | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-55-11 | D00333B | = C71 | | | D04101P | = C1 | | | ALL |
| 01CX | | | | JB A | 5-5 | 34-55-11 | D00333B | 71 | | | D04101P | = A1 | | | ALL |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 | | | | | | | | | | | |
| 001 | 08 | | PA | | 4-0 | 25-53-21 | K00278 | A2 | E | | C00056 | A1 | LA | * | ALL |
| 002 | 08 | | PA | | 4-0 | 25-53-21 | K00278 | B2 | E | | C00056 | B1 | LA | * | ALL |
| 003 | 08 | | PA | | 4-0 | 25-53-21 | K00278 | C2 | E | | C00056 | C1 | LA | * | ALL |
| 004 | 08 | | PA | | 2-0 | 25-53-21 | C00055 | A1 | D | | C00056 | A1 | LA | * | 050-099 |
| 004 | 08 | | PA | | 1-0 | 25-53-21 | C00055 | A1 | D | | C00056 | A1 | LA | * | 150-199, 275-299 |
| 005 | 08 | | PA | | 2-0 | 25-53-21 | C00055 | B1 | D | | C00056 | B1 | LA | * | 050-099 |
| 005 | 08 | | PA | | 1-0 | 25-53-21 | C00055 | B1 | D | | C00056 | B1 | LA | * | 150-199, 275-299 |
| 006 | 08 | | PA | | 2-0 | 25-53-21 | C00055 | C1 | D | | C00056 | C1 | LA | * | 050-099 |
| 006 | 08 | | PA | | 1-0 | 25-53-21 | C00055 | C1 | D | | C00056 | C1 | LA | * | 150-199, 275-299 |
| 007 | 08 | | PA | | 5-0 | 25-53-21 | C00025 | 2 | D | | K00278 | A1 | E | | 050-099 |
| 007 | 08 | | PA | | 6-0 | 25-53-21 | K00278 | A1 | E | | C00025 | 2 | D | | 150-199, 275-299 |
| 008 | 12 | | PA | | 3-0 | 25-53-21 | C00055 | B2 | D | * | C00050 | 2 | D | | 050-099 |
| 008 | 12 | | PA | | 4-0 | 25-53-21 | C00055 | B2 | D | * | C00050 | 2 | D | | 150-199 |
| 008 | 12 | | PA | | 3-0 | 25-53-21 | C00055 | B2 | D | * | C00080 | 2 | D | | 275-299 |
| 009 | 22 | | PA | | 6-0 | 25-53-23 | TB0122D | C | 2 | | S00392 | 10 | C | | 050-099 |
| 010 | 22 | | PA | | 6-0 | 25-53-23 | TB0122D | C | 2 | | S00392 | 8 | C | * | 050-099 |
| 011 | 12 | | PA | | 3-0 | 25-53-21 | C00055 | A2 | D | | C00036 | A1 | D | * | 050-099 |
| 011 | 12 | | PA | | 3-0 | 25-53-21 | C00055 | A2 | D | | C00162 | A1 | D | * | 150-199, 275-299 |
| 012 | 12 | | PA | | 3-0 | 25-53-21 | C00036 | A1 | D | * | C00037 | A1 | D | * | 050-099 |
| 012 | 12 | | PA | | 1-0 | 25-53-21 | C00162 | A1 | D | * | C00163 | A1 | D | * | 150-199, 275-299 |
| 013 | 12 | | PA | | 2-0 | 25-53-21 | C00037 | A1 | D | * | C00038 | A1 | D | * | 050-099 |
| 013 | 12 | | PA | | 1-0 | 25-53-21 | C00163 | A1 | D | * | C00164 | A1 | D | * | 150-199, 275-299 |
| 014 | 12 | | PA | | 2-0 | 25-53-21 | C00038 | A1 | D | * | C00039 | A1 | D | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 58

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | |
| 014 | 12 | PA | | 1-0 | 25-53-21 | C00164 | A1 | D | * | C00165 | A1 | D | | 150-199, 275-299 | | |
| 015 | 12 | PA | | 3-0 | 25-53-21 | C00056 | A2 | D | | C00040 | A2 | D | * | 050-099 | | |
| 015 | 12 | PA | | 3-0 | 25-53-21 | C00056 | A2 | D | | C00158 | A2 | D | * | 150-199, 275-299 | | |
| 016 | 12 | PA | | 2-0 | 25-53-21 | C00040 | A2 | D | * | C00041 | A2 | D | * | 050-099 | | |
| 016 | 12 | PA | | 1-0 | 25-53-21 | C00158 | A2 | D | * | C00159 | A2 | D | * | 150-199, 275-299 | | |
| 017 | 12 | PA | | 2-0 | 25-53-21 | C00041 | A2 | D | * | C00042 | A2 | D | * | 050-099 | | |
| 017 | 12 | PA | | 1-0 | 25-53-21 | C00159 | A2 | D | * | C00160 | A2 | D | * | 150-199, 275-299 | | |
| 018 | 12 | PA | | 2-0 | 25-53-21 | C00042 | A2 | D | * | C00043 | A2 | D | | 050-099 | | |
| 018 | 12 | PA | | 1-0 | 25-53-21 | C00160 | A2 | D | * | C00161 | A2 | D | | 150-199, 275-299 | | |
| 021 | 12 | PA | | 3-0 | 25-53-21 | C00055 | B2 | D | * | C00036 | B1 | D | * | 050-099 | | |
| 021 | 12 | PA | | 3-0 | 25-53-21 | C00055 | B2 | D | * | C00162 | B1 | D | * | 150-199, 275-299 | | |
| 022 | 12 | PA | | 2-0 | 25-53-21 | C00036 | B1 | D | * | C00037 | B1 | D | * | 050-099 | | |
| 022 | 12 | PA | | 1-0 | 25-53-21 | C00162 | B1 | D | * | C00163 | B1 | D | * | 150-199, 275-299 | | |
| 023 | 12 | PA | | 2-0 | 25-53-21 | C00037 | B1 | D | * | C00038 | B1 | D | * | 050-099 | | |
| 023 | 12 | PA | | 1-0 | 25-53-21 | C00163 | B1 | D | * | C00164 | B1 | D | * | 150-199, 275-299 | | |
| 024 | 12 | PA | | 2-0 | 25-53-21 | C00038 | B1 | D | * | C00039 | B1 | D | | 050-099 | | |
| 024 | 12 | PA | | 1-0 | 25-53-21 | C00164 | B1 | D | * | C00165 | B1 | D | | 150-199, 275-299 | | |
| 025 | 12 | PA | | 3-0 | 25-53-21 | C00056 | B2 | D | | C00040 | B2 | D | * | 050-099 | | |
| 025 | 12 | PA | | 2-0 | 25-53-21 | C00056 | B2 | D | | C00158 | B2 | D | * | 150-199, 275-299 | | |
| 026 | 12 | PA | | 2-0 | 25-53-21 | C00040 | B2 | D | * | C00041 | B2 | D | * | 050-099 | | |
| 026 | 12 | PA | | 1-0 | 25-53-21 | C00158 | B2 | D | * | C00159 | B2 | D | * | 150-199, 275-299 | | |
| 027 | 12 | PA | | 2-0 | 25-53-21 | C00041 | B2 | D | * | C00042 | B2 | D | * | 050-099 | | |
| 027 | 12 | PA | | 1-0 | 25-53-21 | C00159 | B2 | D | * | C00160 | B2 | D | * | 150-199, 275-299 | | |
| 028 | 12 | PA | | 2-0 | 25-53-21 | C00042 | B2 | D | * | C00043 | B2 | D | | 050-099 | | |
| 028 | 12 | PA | | 1-0 | 25-53-21 | C00160 | B2 | D | * | C00161 | B2 | D | | 150-199, 275-299 | | |
| 031 | 12 | PA | | 3-0 | 25-53-21 | C00055 | C2 | D | | C00036 | C1 | D | * | 050-099 | | |
| 031 | 12 | PA | | 3-0 | 25-53-21 | C00055 | C2 | D | | C00162 | C1 | D | * | 150-199, 275-299 | | |
| 032 | 12 | PA | | 2-0 | 25-53-21 | C00036 | C1 | D | * | C00037 | C1 | D | * | 050-099 | | |
| 032 | 12 | PA | | 1-0 | 25-53-21 | C00162 | C1 | D | * | C00163 | C1 | D | * | 150-199, 275-299 | | |
| 033 | 12 | PA | | 2-0 | 25-53-21 | C00037 | C1 | D | * | C00038 | C1 | D | * | 050-099 | | |
| 033 | 12 | PA | | 1-0 | 25-53-21 | C00163 | C1 | D | * | C00164 | C1 | D | * | 150-199, 275-299 | | |
| 034 | 12 | PA | | 2-0 | 25-53-21 | C00038 | C1 | D | * | C00039 | C1 | D | | 050-099 | | |
| 034 | 12 | PA | | 1-0 | 25-53-21 | C00164 | C1 | D | * | C00165 | C1 | D | | 150-199, 275-299 | | |
| 035 | 12 | PA | | 3-0 | 25-53-21 | C00056 | C2 | D | | C00040 | C2 | D | * | 050-099 | | |
| 035 | 12 | PA | | 2-0 | 25-53-21 | C00056 | C2 | D | | C00158 | C2 | D | * | 150-199, 275-299 | | |
| 036 | 12 | PA | | 2-0 | 25-53-21 | C00040 | C2 | D | * | C00041 | C2 | D | * | 050-099 | | |
| 036 | 12 | PA | | 1-0 | 25-53-21 | C00158 | C2 | D | * | C00159 | C2 | D | * | 150-199, 275-299 | | |
| 037 | 12 | PA | | 2-0 | 25-53-21 | C00041 | C2 | D | * | C00042 | C2 | D | * | 050-099 | | |
| 037 | 12 | PA | | 1-0 | 25-53-21 | C00159 | C2 | D | * | C00160 | C2 | D | * | 150-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 59

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | |
| 038 | 12 | | PA | | 2-0 | 25-53-21 | C00042 | C2 | D | * | C00043 | C2 | D | | 050-099 |
| 038 | 12 | | PA | | 1-0 | 25-53-21 | C00160 | C2 | D | * | C00161 | C2 | D | | 150-199, 275-299 |
| 041 | 18 | | PA | | 3-0 | 33-37-21 | D05888J | 13 | DK | | D05616J | 14 | | | 050-099 |
| 041 | 16 | | PA | | 2-0 | 33-37-21 | D05888J | 13 | FM | | D05616J | 14 | | | 150-199, 275-299 |
| 042 | 20 | | PA | | 5-0 | 33-37-21 | D05888J | 14 | | | S00429 | 1 | C | * | 050-099 |
| 042 | 18 | | PA | | 4-0 | 33-37-21 | D05888J | 14 | DK | | S00429 | 1 | C | * | 150-199, 275-299 |
| 043 | 20 | | PA | | 5-0 | 33-37-21 | D05888J | 15 | | | S00429 | 3 | C | * | 050-099 |
| 043 | 18 | | PA | | 4-0 | 33-37-21 | D05888J | 15 | DK | | S00429 | 3 | C | * | 150-199, 275-299 |
| 044 | 20 | | PA | | 1-0 | 33-37-21 | S00429 | 6 | C | | S00429 | 1 | C | * | 050-099 |
| 044 | 18 | | PA | | 1-0 | 33-37-21 | S00429 | 6 | C | | S00429 | 1 | C | * | 150-199, 275-299 |
| 045 | 20 | | PA | | 1-0 | 33-37-21 | S00429 | 4 | C | | S00429 | 3 | C | * | 050-099 |
| 045 | 18 | | PA | | 1-0 | 33-37-21 | S00429 | 4 | C | | S00429 | 3 | C | * | 150-199, 275-299 |
| 046 | 20 | | PA | | 5-0 | 33-37-21 | S00429 | 2 | C | | D04312J | 25 | | | 050-099 |
| 046 | 18 | | PA | | 4-0 | 33-37-21 | S00429 | 2 | C | | D04312J | 24 | DK | | 150-199, 275-299 |
| 047 | 20 | | PA | | 5-0 | 33-37-21 | S00429 | 5 | C | | D04312J | 26 | | | 050-099 |
| 047 | 18 | | PA | | 10-0 | 33-37-21 | S00429 | 5 | C | | D04312J | 26 | DK | | 150-199, 275-299 |
| 048 | 18 | | PA | | 2-0 | 33-37-21 | D02630 | A1 | | | TB0120G | 20 | 2 | | 050-099 |
| 048 | 16 | | PA | | 3-0 | 33-37-21 | D02630 | A1 | | | TB0120G | 20 | 2 | | 150-199, 275-299 |
| 050 | 18 | | PA | | 5-0 | 33-37-21 | T00152 | HV1 | E | * | D02630 | A2 | | | 050-099 |
| 050 | 16 | | PA | | 5-0 | 33-37-21 | T00152 | HV1 | E | * | D02630 | A2 | | | 150-199, 275-299 |
| 051 | 12 | | PA | | 4-0 | 33-37-21 | T00152 | GND | E | | D05616J | 18 | | | 050-099 |
| 051 | 12 | | PA | | 3-0 | 33-37-21 | T00152 | GND | E | | D05616J | 18 | | | 150-199, 275-299 |
| 052 | 12 | | PA | | 6-0 | 33-37-21 | T00152 | LV | E | | C00065 | 2 | D | | ALL |
| 053 | 18 | | PA | | 5-0 | 33-37-21 | C00065 | 1 | D | | D04312J | 21 | | | 050-099 |
| 053 | 16 | | PA | | 4-0 | 33-37-21 | C00065 | 1 | D | | D04312J | 21 | | | 150-199, 275-299 |
| 054 | 18 | | PA | | 5-0 | 33-37-21 | C00066 | 1 | D | | D04312J | 23 | | | 050-099 |
| 054 | 16 | | PA | | 4-0 | 33-37-21 | C00066 | 1 | D | | D04312J | 23 | | | 150-199, 275-299 |
| 055 | 20 | | PA | | 6-0 | 33-37-21 | C00064 | 1 | D | | D02628 | A1 | | | 050-099 |
| 055 | 18 | | PA | | 6-0 | 33-37-21 | C00064 | 1 | D | | D02628 | A1 | | | 150-199, 275-299 |
| 056 | 20 | | PA | | 5-0 | 33-37-21 | D04312J | 20 | | | D02628 | A2 | | | 050-099 |
| 056 | 18 | | PA | | 4-0 | 33-37-21 | D04312J | 20 | DK | | D02628 | A2 | | | 150-199, 275-299 |
| 057 | 20 | | PA | | 5-0 | 33-31-61 | C00025 | 1 | D | | D05888J | 11 | | | ALL |
| 058 | 20 | | PA | | 3-0 | 33-31-61 | T00151 | HV1 | E | | D05888J | 12 | | | ALL |
| 059 | 16 | | PA | | 3-0 | 33-31-61 | T00151 | GND | E | | D05616J | 20 | | | 050-099, 150-199 |
| 059 | 16 | | PA | | 4-0 | 33-31-61 | T00151 | GND | E | | D05616J | 20 | | | 275-299 |
| 060 | 16 | | PA | | 6-0 | 33-31-61 | T00151 | LV | E | | C00017 | 2 | D | | 050-099 |
| 060 | 16 | | PA | | 6-0 | 33-31-61 | C00017 | 2 | D | | T00151 | LV | E | | 150-199, 275-299 |
| 061 | 20 | | PA | | 6-0 | 33-31-61 | D02628 | B1 | | | C00017 | 1 | D | | 050-099 |
| 061 | 20 | | PA | | 6-0 | 33-31-61 | C00017 | 1 | D | | D02628 | B1 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 60

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | | |
| 062 | 20 | | PA | 5-0 | 33-31-61 | D02628 | | B2 | | | | | D04312J | 17 | | | ALL |
| 063 | 20 | | PA | 5-0 | 33-31-61 | C00019 | | 1 | D | | | | D04312J | 18 | | | ALL |
| 064 | 20 | | PA | 5-0 | 33-31-61 | C00024 | | 1 | D | | | | D04312J | 19 | | | 050-099 |
| 064 | 20 | | PA | 5-0 | 33-31-61 | D04312J | | 19 | | | | | C00024 | 1 | D | | 150-199 |
| 065 | 18 | | PA | 4-0 | 33-37-21 | D04312J | | 27 | DK | | | | TB0120G | 20 | 2 | | 050-099 |
| 065 | 16 | | PA | 4-0 | 33-37-21 | D04312J | | 27 | FM | | | | TB0120G | 20 | 2 | | 150-199, 275-299 |
| 066 | 18 | | PA | 3-0 | 33-37-21 | D02628 | | C1 | | | | | TB0120G | 20 | 2 | | 050-099 |
| 066 | 16 | | PA | 3-0 | 33-37-21 | D02628 | | C1 | | | | | TB0120G | 20 | 2 | | 150-199, 275-299 |
| 067 | 18 | | PA | 6-0 | 33-37-21 | D02628 | | C2 | | | | | T00152 | HV1 | E | * | 050-099 |
| 067 | 16 | | PA | 5-0 | 33-37-21 | D02628 | | C2 | | | | | T00152 | HV1 | E | * | 150-199, 275-299 |
| 071 | 22 | | PA | 2-0 | 25-53-25 | TB0120H | | 7 | 2 | | | | D02558 | A2 | | | 050-099 |
| 071 | 22 | | PA | 4-0 | 25-53-25 | TB0120H | | 7 | 2 | | | | D02558 | A2 | | | 150-199, 275-299 |
| 072 | 22 | | PA | 2-0 | 25-53-25 | TB0120H | | 7 | 2 | | | | D02558 | B2 | | | 050-099 |
| 072 | 22 | | PA | 4-0 | 25-53-25 | D02558 | | B2 | | | | | TB0120H | 7 | 2 | | 150-199, 275-299 |
| 073 | 22 | | PA | 2-0 | 25-53-25 | D02558 | | C2 | | | | | TB0120H | 7 | 2 | | 050-099 |
| 073 | 22 | | PA | 4-0 | 25-53-25 | D02558 | | C2 | | | | | TB0120H | 7 | 2 | | 150-199, 275-299 |
| 081 | 22 | | PA | 2-0 | 25-53-25 | TB0120H | | 7 | 2 | | | | D02560 | A2 | | | 050-099 |
| 081 | 22 | | PA | 4-0 | 25-53-25 | TB0120H | | 7 | 2 | | | | D02560 | A2 | | | 150-199, 275-299 |
| 082 | 22 | | PA | 2-0 | 25-53-25 | TB0120H | | 7 | 2 | | | | D02560 | B2 | | | 050-099 |
| 082 | 22 | | PA | 4-0 | 25-53-25 | D02560 | | B2 | | | | | TB0120H | 7 | 2 | | 150-199, 275-299 |
| 083 | 22 | | PA | 2-0 | 25-53-25 | D02560 | | C2 | | | | | TB0120H | 7 | 2 | | 050-099 |
| 083 | 22 | | PA | 4-0 | 25-53-25 | D02560 | | C2 | | | | | TB0120H | 7 | 2 | | 150-199, 275-299 |
| 092 | 22 | | PA | 3-0 | 25-53-26 | D02554 | | C2 | | | | | TB0120H | 1 | 2 | | 050-099 |
| 092 | 22 | | PA | 5-0 | 25-53-26 | D02554 | | C2 | | | | | TB0120H | 1 | 2 | | 150-199, 275-299 |
| 093 | 22 | | PA | 3-0 | 25-53-26 | D02554 | | D2 | | | | | TB0120H | 1 | 2 | | 050-099 |
| 093 | 22 | | PA | 5-0 | 25-53-26 | D02554 | | D2 | | | | | TB0120H | 1 | 2 | | 150-199, 275-299 |
| 094 | 22 | | PA | 3-0 | 25-53-26 | D02556 | | A2 | | | | | TB0120H | 1 | 2 | | 050-099 |
| 094 | 22 | | PA | 4-0 | 25-53-26 | D02556 | | A2 | | | | | TB0120H | 1 | 2 | | 150-199, 275-299 |
| 095 | 22 | | PA | 3-0 | 25-53-26 | D02556 | | B2 | | | | | TB0120H | 1 | 2 | | 050-099 |
| 095 | 22 | | PA | 4-0 | 25-53-26 | D02556 | | B2 | | | | | TB0120H | 1 | 2 | | 150-199, 275-299 |
| 096 | 22 | | PA | 1-0 | 25-53-27 | TB0120H | | 1 | 2 | | | | TB0120H | 3 | 2 | | 050-099 |
| 096 | 22 | | PA | 2-0 | 25-53-27 | TB0120H | | 1 | 2 | | | | TB0120H | 3 | 2 | | 150-199 |
| 097 | 22 | | PA | 2-0 | 25-53-27 | D02562 | | B2 | | | | | TB0120H | 3 | 2 | | 050-099 |
| 097 | 22 | | PA | 4-0 | 25-53-27 | D02562 | | B2 | | | | | TB0120H | 3 | 2 | | 150-199 |
| 098 | 22 | | PA | 2-0 | 25-53-27 | D02562 | | A2 | | | | | TB0120H | 3 | 2 | | 050-099 |
| 098 | 22 | | PA | 4-0 | 25-53-27 | D02562 | | A2 | | | | | TB0120H | 3 | 2 | | 150-199 |
| 099 | 22 | | PA | 2-0 | 25-53-27 | D02564 | | B2 | | | | | TB0120H | 3 | 2 | | 050-099 |
| 099 | 22 | | PA | 4-0 | 25-53-27 | D02564 | | B2 | | | | | TB0120H | 3 | 2 | | 150-199 |
| 100 | 22 | | PA | 2-0 | 25-53-27 | D02564 | | A2 | | | | | TB0120H | 3 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 61

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | |
| 100 | 22 | | PA | 4-0 | 25-53-27 | D02564 | A2 | | | | TB0120H | 3 | 2 | | 150-199 |
| 101 | 22 | | PA | 4-0 | 25-53-25 | D05252J | 1 | | | | D02558 | A3 | | | ALL |
| 102 | 22 | | PA | 4-0 | 25-53-25 | D05252J | 2 | | | | D02558 | A1 | | | ALL |
| 103 | 22 | | PA | 4-0 | 25-53-25 | D05252J | 3 | | | | D02558 | B3 | | | ALL |
| 104 | 22 | | PA | 4-0 | 25-53-25 | D05252J | 4 | | | | D02558 | B1 | | | ALL |
| 105 | 22 | | PA | 4-0 | 25-53-25 | D05252J | 5 | | | | D02558 | C3 | | | ALL |
| 106 | 22 | | PA | 4-0 | 25-53-25 | D05252J | 6 | | | | D02558 | C1 | | | ALL |
| 107 | 22 | | PA | 4-0 | 25-53-25 | D05252J | 7 | | | | D02560 | A3 | | | ALL |
| 108 | 22 | | PA | 4-0 | 25-53-25 | D05252J | 8 | | | | D02560 | A1 | | | ALL |
| 109 | 22 | | PA | 4-0 | 25-53-25 | D05252J | 9 | | | | D02560 | B3 | | | ALL |
| 110 | 22 | | PA | 4-0 | 25-53-25 | D05252J | 10 | | | | D02560 | B1 | | | ALL |
| 111 | 22 | | PA | 4-0 | 25-53-25 | D05252J | 11 | | | | D02560 | C3 | | | ALL |
| 112 | 22 | | PA | 4-0 | 25-53-25 | D05252J | 12 | | | | D02560 | C1 | | | ALL |
| 113 | 22 | | PA | 5-0 | 25-53-26 | D05252J | 13 | | | | D02554 | A3 | | | 050-099 |
| 113 | 22 | | PA | 4-0 | 25-53-26 | D05252J | 13 | | | | D02554 | A3 | | | 150-199, 275-299 |
| 114 | 22 | | PA | 4-0 | 25-53-26 | D05252J | 14 | | | | TB0120G | 13 | 2 | | ALL |
| 115 | 22 | | PA | 5-0 | 25-53-26 | D05252J | 15 | | | | D02554 | B3 | | | 050-099 |
| 115 | 22 | | PA | 4-0 | 25-53-26 | D05252J | 15 | | | | D02554 | B3 | | | 150-199, 275-299 |
| 116 | 22 | | PA | 4-0 | 25-53-26 | D05252J | 16 | | | | TB0120G | 14 | 2 | | ALL |
| 117 | 22 | | PA | 5-0 | 25-53-26 | D05252J | 17 | | | | D02554 | C1 | | | 050-099 |
| 117 | 22 | | PA | 4-0 | 25-53-26 | D05252J | 17 | | | | D02554 | C1 | | | 150-199, 275-299 |
| 118 | 22 | | PA | 5-0 | 25-53-26 | D05252J | 18 | | | | D02554 | C3 | | | 050-099 |
| 118 | 22 | | PA | 4-0 | 25-53-26 | D05252J | 18 | | | | D02554 | C3 | | | 150-199, 275-299 |
| 119 | 22 | | PA | 5-0 | 25-53-26 | D05252J | 19 | | | | D02554 | D1 | | | 050-099 |
| 119 | 22 | | PA | 4-0 | 25-53-26 | D05252J | 19 | | | | D02554 | D1 | | | 150-199, 275-299 |
| 120 | 22 | | PA | 5-0 | 25-53-26 | D05252J | 20 | | | | D02554 | D3 | | | 050-099 |
| 120 | 22 | | PA | 4-0 | 25-53-26 | D05252J | 20 | | | | D02554 | D3 | | | 150-199, 275-299 |
| 121 | 22 | | PA | 4-0 | 25-53-27 | D05252J | 21 | | | | D02564 | B1 | | | 050-099 |
| 121 | 22 | | PA | 5-0 | 25-53-27 | D05252J | 21 | | | | D02564 | B1 | | | 150-199 |
| 122 | 22 | | PA | 4-0 | 25-53-27 | D05252J | 22 | | | | D02564 | B3 | | | 050-099 |
| 122 | 22 | | PA | 5-0 | 25-53-27 | D05252J | 22 | | | | D02564 | B3 | | | 150-199 |
| 123 | 22 | | PA | 4-0 | 25-53-27 | D05252J | 23 | | | | D02562 | B3 | | | 050-099 |
| 123 | 22 | | PA | 5-0 | 25-53-27 | D05252J | 23 | | | | D02562 | B3 | | | 150-199 |
| 124 | 22 | | PA | 4-0 | 25-53-27 | D05252J | 24 | | | | D02564 | A1 | | | 050-099 |
| 124 | 22 | | PA | 5-0 | 25-53-27 | D05252J | 24 | | | | D02564 | A1 | | | 150-199 |
| 125 | 22 | | PA | 4-0 | 25-53-27 | D05252J | 25 | | | | D02564 | A3 | | | 050-099 |
| 125 | 22 | | PA | 5-0 | 25-53-27 | D02564 | A3 | | | | D05252J | 25 | | | 150-199 |
| 126 | 22 | | PA | 4-0 | 25-53-27 | D05252J | 26 | | | | D02562 | A3 | | | 050-099 |
| 126 | 22 | | PA | 5-0 | 25-53-27 | D05252J | 26 | | | | D02562 | A3 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 62

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | |
| 130 | 22 | | PA | 1-0 | 25-53-26 | D02556 | | A3 | | | | D02554 | A2 | | | ALL |
| 131 | 22 | | PA | 3-0 | 25-53-26 | D02556 | | A1 | | | | TB0120G | 13 | 2 | | 050-099 |
| 131 | 22 | | PA | 4-0 | 25-53-26 | D02556 | | A1 | | | | TB0120G | 13 | 2 | | 150-199, 275-299 |
| 132 | 22 | | PA | 3-0 | 25-53-26 | D02554 | | A1 | | | | TB0120G | 13 | 2 | | 050-099 |
| 132 | 22 | | PA | 4-0 | 25-53-26 | D02554 | | A1 | | | | TB0120G | 13 | 2 | | 150-199, 275-299 |
| 133 | 22 | | PA | 1-0 | 25-53-26 | D02556 | | B3 | | | | D02554 | B2 | | | ALL |
| 134 | 22 | | PA | 3-0 | 25-53-26 | D02556 | | B1 | | | | TB0120G | 14 | 2 | | 050-099 |
| 134 | 22 | | PA | 4-0 | 25-53-26 | D02556 | | B1 | | | | TB0120G | 14 | 2 | | 150-199, 275-299 |
| 135 | 22 | | PA | 3-0 | 25-53-26 | D02554 | | B1 | | | | TB0120G | 14 | 2 | | 050-099 |
| 135 | 22 | | PA | 4-0 | 25-53-26 | D02554 | | B1 | | | | TB0120G | 14 | 2 | | 150-199, 275-299 |
| 141 | 20 | | PA | 5-0 | 52-35-11 | D02510 | | A2 | | | | D05616J | 11 | | | 050-099 |
| 141 | 20 | | PA | 4-0 | 52-35-11 | D02510 | | A2 | | | | D05616J | 11 | | | 150-199, 275-299 |
| 142 | 20 | | PA | 5-0 | 52-35-11 | D02510 | | B2 | | | | D05616J | 12 | | | 050-099 |
| 142 | 20 | | PA | 4-0 | 52-35-11 | D02510 | | B2 | | | | D05616J | 12 | | | 150-199, 275-299 |
| 143 | 20 | | PA | 5-0 | 52-35-11 | D02510 | | C2 | | | | D05616J | 13 | | | 050-099 |
| 143 | 20 | | PA | 4-0 | 52-35-11 | D02510 | | C2 | | | | D05616J | 13 | | | 150-199, 275-299 |
| 144 | 20 | | PA | 2-0 | 52-35-11 | D02510 | | A1 | | | | TB0118G | 45 | 2 | | ALL |
| 145 | 20 | | PA | 2-0 | 52-35-11 | D02510 | | B1 | | | | TB0118G | 46 | 2 | | ALL |
| 146 | 20 | | PA | 2-0 | 52-35-11 | D02510 | | C1 | | | | TB0118G | 47 | 2 | | ALL |
| 149 | 22 | | PA | 4-0 | 25-53-23 | D02544 | | 6 | | | | TB0118Z | 17 | BJ | | 150-199, 275-299 |
| 150 | 22 | | PA | 2-0 | 25-53-23 | L00819 | | =P | \$ | * | | L00820 | =P | \$ | * | 150-199, 275-299 |
| 151 | 20 | | PA | 2-0 | 52-35-11 | D02516 | | A2 | | | | TB0118G | 45 | 2 | | 050-099 |
| 151 | 20 | | PA | 1-0 | 52-35-11 | D02516 | | A2 | | | | TB0118G | 45 | 2 | | 150-199, 275-299 |
| 152 | 20 | | PA | 2-0 | 52-35-11 | D02516 | | B2 | | | | TB0118G | 46 | 2 | | 050-099 |
| 152 | 20 | | PA | 1-0 | 52-35-11 | D02516 | | B2 | | | | TB0118G | 46 | 2 | | 150-199, 275-299 |
| 153 | 20 | | PA | 2-0 | 52-35-11 | D02516 | | C2 | | | | TB0118G | 47 | 2 | | 050-099 |
| 153 | 20 | | PA | 1-0 | 52-35-11 | D02516 | | C2 | | | | TB0118G | 47 | 2 | | 150-199, 275-299 |
| 154 | 20 | | PA | 2-0 | 52-35-11 | D02516 | | A1 | | | | D02518 | A3 | | | 050-099 |
| 154 | 20 | | PA | 1-0 | 52-35-11 | D02516 | | A1 | | | | D02518 | A3 | | | 150-199, 275-299 |
| 155 | 20 | | PA | 2-0 | 52-35-11 | D02516 | | B1 | | | | D02518 | B3 | | | 050-099 |
| 155 | 20 | | PA | 1-0 | 52-35-11 | D02516 | | B1 | | | | D02518 | B3 | | | 150-199, 275-299 |
| 156 | 20 | | PA | 2-0 | 52-35-11 | D02516 | | C1 | | | | D02518 | C3 | | | 050-099 |
| 156 | 20 | | PA | 1-0 | 52-35-11 | D02516 | | C1 | | | | D02518 | C3 | | | 150-199, 275-299 |
| 157 | 20 | | PA | 2-0 | 52-35-11 | D02516 | | A3 | | | | D02518 | A1 | | | 050-099 |
| 157 | 20 | | PA | 1-0 | 52-35-11 | D02516 | | A3 | | | | D02518 | A1 | | | 150-199, 275-299 |
| 158 | 20 | | PA | 2-0 | 52-35-11 | D02516 | | B3 | | | | D02518 | C1 | | | 050-099 |
| 158 | 20 | | PA | 1-0 | 52-35-11 | D02516 | | B3 | | | | D02518 | C1 | | | 150-199, 275-299 |
| 159 | 20 | | PA | 2-0 | 52-35-11 | D02516 | | C3 | | | | D02518 | B1 | | | 050-099 |
| 159 | 20 | | PA | 1-0 | 52-35-11 | D02516 | | C3 | | | | D02518 | B1 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 63

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | | |
| 161 | 20 | PA | | | 2-0 | 52-35-11 | D02512 | | A2 | | | | TB0118G | 45 | 2 | | ALL |
| 162 | 20 | PA | | | 2-0 | 52-35-11 | D02512 | | B2 | | | | TB0118G | 46 | 2 | | ALL |
| 163 | 20 | PA | | | 2-0 | 52-35-11 | D02512 | | C2 | | | | TB0118G | 47 | 2 | | ALL |
| 164 | 20 | PA | | | 2-0 | 52-35-11 | D02512 | | A1 | | | | D02514 | A3 | | | 050-099 |
| 164 | 20 | PA | | | 1-0 | 52-35-11 | D02512 | | A1 | | | | D02514 | A3 | | | 150-199, 275-299 |
| 165 | 20 | PA | | | 2-0 | 52-35-11 | D02512 | | B1 | | | | D02514 | B3 | | | 050-099 |
| 165 | 20 | PA | | | 1-0 | 52-35-11 | D02512 | | B1 | | | | D02514 | B3 | | | 150-199, 275-299 |
| 166 | 20 | PA | | | 2-0 | 52-35-11 | D02512 | | C1 | | | | D02514 | C3 | | | 050-099 |
| 166 | 20 | PA | | | 1-0 | 52-35-11 | D02512 | | C1 | | | | D02514 | C3 | | | 150-199, 275-299 |
| 167 | 20 | PA | | | 2-0 | 52-35-11 | D02512 | | A3 | | | | D02514 | A1 | | | 050-099 |
| 167 | 20 | PA | | | 1-0 | 52-35-11 | D02512 | | A3 | | | | D02514 | A1 | | | 150-199, 275-299 |
| 168 | 20 | PA | | | 2-0 | 52-35-11 | D02512 | | B3 | | | | D02514 | C1 | | | 050-099 |
| 168 | 20 | PA | | | 1-0 | 52-35-11 | D02512 | | B3 | | | | D02514 | C1 | | | 150-199, 275-299 |
| 169 | 20 | PA | | | 2-0 | 52-35-11 | D02512 | | C3 | | | | D02514 | B1 | | | 050-099 |
| 169 | 20 | PA | | | 1-0 | 52-35-11 | D02512 | | C3 | | | | D02514 | B1 | | | 150-199, 275-299 |
| 170 | 22 | PA | | | 4-0 | 25-53-26 | TB0118Z | | 41 | BJ | | | TB0122H | 5 | 2 | | 050-099 |
| 170 | 22 | PA | | | 2-0 | 25-53-26 | TB0118Z | | 36 | BJ | | | TB0118Z | 39 | BJ | | 150-199, 275-299 |
| 171 | 20 | PA | | | 4-0 | 52-35-11 | D02518 | | A2 | | | | D04312J | 11 | | | ALL |
| 172 | 20 | PA | | | 4-0 | 52-35-11 | D02518 | | B2 | | | | D04312J | 12 | | | ALL |
| 173 | 20 | PA | | | 4-0 | 52-35-11 | D02518 | | C2 | | | | D04312J | 13 | | | ALL |
| 174 | 20 | PA | | | 4-0 | 52-35-11 | D02514 | | A2 | | | | D04312J | 14 | | | ALL |
| 175 | 20 | PA | | | 4-0 | 52-35-11 | D02514 | | B2 | | | | D04312J | 15 | | | ALL |
| 176 | 20 | PA | | | 4-0 | 52-35-11 | D02514 | | C2 | | | | D04312J | 16 | | | ALL |
| 177 | 22 | PA | | | 4-0 | 25-53-27 | D02562 | | X2 | | | | TB0120H | 5 | 2 | | 150-199 |
| 178 | 22 | PA | | | 7-0 | 25-53-27 | TB0120H | | 5 | 2 | | | TB0308Z | 8 | BJ | | 150-199 |
| 179 | 22 | PA | | | 7-0 | 25-53-26 | D11664 | | 2 | | | | TB0308Z | 11 | BJ | | 050-099 |
| 180 | 22 | PA | | | 7-0 | 25-53-25 | C00075 | | 1 | D | * | | TB0308Z | 12 | BJ | | 050-099 |
| 180 | 22 | PA | | | 6-0 | 25-53-25 | C00075 | | 1 | D | | | TB0308Z | 12 | BJ | | 150-199, 275-299 |
| 181 | 22 | PA | | | 7-0 | 25-53-26 | D11852 | | 4 | | | | TB0308Y | C001 | BJ | | 050-099 |
| 181 | 22 | PA | | | 3-0 | 25-53-26 | D11852 | | 4 | | | | TB0118G | 55 | 2 | | 150-199, 275-299 |
| 182 | 22 | PA | | | 6-0 | 25-53-26 | TB0308Y | | C002 | BJ | | | TB0120D | A021 | 2 | | 050-099 |
| 182 | 22 | PA | | | 6-0 | 25-53-26 | D11668 | | 8 | | | | TB0308Y | C002 | BJ | | 150-199, 275-299 |
| 183 | 22 | PA | | | 4-0 | 25-53-23 | D05250J | | 13 | | | | TB0118Z | 34 | BJ | | 150-199, 275-299 |
| 184 | 22 | PA | | | 4-0 | 25-53-24 | D11198 | | C2 | | | | TB0118Z | 51 | BJ | | 150-199, 275-299 |
| 188 | 22 | PA | | | 3-0 | 25-53-26 | D11668 | | 7 | | | | TB0118Z | 52 | BJ | | 150-199, 275-299 |
| 189 | 22 | PA | | | 2-0 | 25-53-26 | D11668 | | 3 | | | | TB0118Z | 41 | BJ | | 050-099 |
| 189 | 22 | PA | | | 4-0 | 25-53-26 | D11668 | | 3 | | | | TB0118Z | 36 | BJ | | 150-199, 275-299 |
| 190 | 22 | PA | | | 4-0 | 25-53-26 | D11198 | | D2 | | | | TB0118Z | 36 | BJ | | 150-199, 275-299 |
| 191 | 22 | PA | | | 1-0 | 25-53-26 | D02538 | | D3 | | | | D11664 | 3 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 64

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | |
| 191 | 22 | | PA | | 2-0 | 25-53-26 | D11198 | | D3 | | | | | | | 150-199, 275-299 |
| 192 | 22 | | PA | | 4-0 | 25-53-26 | D11664 | | 7 | | | | C022 | 2 | | 050-099 |
| 192 | 22 | | PA | | 4-0 | 25-53-26 | D11664 | | 7 | | | | C012 | 2 | | 150-199, 275-299 |
| 193 | 22 | | PA | | 3-0 | 25-53-26 | D11664 | | 2 | | | | 33 | BJ | | 150-199, 275-299 |
| 194 | 22 | | PA | | 3-0 | 25-53-26 | D11664 | | 6 | | | | A054 | BJ | | 050-099 |
| 194 | 22 | | PA | | 3-0 | 25-53-26 | D11664 | | 6 | | | | 51 | BJ | | 150-199, 275-299 |
| 195 | 22 | | PA | | 1-0 | 25-53-26 | TB0120D | | A022 | 2 | | | C021 | 2 | | 050-099 |
| 195 | 22 | | PA | | 2-0 | 25-53-26 | TB0122D | | A012 | 2 | | | C011 | 2 | | 150-199, 275-299 |
| 196 | 22 | | PA | | 4-0 | 25-53-26 | D11664 | | 5 | | | | C022 | 2 | | 050-099 |
| 196 | 22 | | PA | | 4-0 | 25-53-26 | D11664 | | 5 | | | | C012 | 2 | | 150-199, 275-299 |
| 201B | 24 | | PL | A | 2-0 | 52-71-13 | D08072J | | 1 | | | | | 1 | | ALL |
| 201R | 24 | | PL | A | 0-0 | 52-71-13 | D08072J | | 2 | | | | | 2 | | ALL |
| 202B | 24 | | PL | B | 2-0 | 52-35-13 | D08072J | | 3 | | | | | 3 | | ALL |
| 202R | 24 | | PL | B | 0-0 | 52-35-13 | D08072J | | 4 | | | | | 4 | | ALL |
| 203B | 24 | | PL | C | 2-0 | 52-35-13 | D08072J | | 5 | | | | | 5 | | ALL |
| 203R | 24 | | PL | C | 0-0 | 52-35-13 | D08072J | | 6 | | | | | 6 | | ALL |
| 204B | 24 | | PL | D | 2-0 | 52-35-13 | D08072J | | 7 | | | | | 7 | | ALL |
| 204R | 24 | | PL | D | 0-0 | 52-35-13 | D08072J | | 8 | | | | | 8 | | ALL |
| 205B | 24 | | PL | E | 2-0 | 52-35-13 | D08072J | | 9 | | | | | 9 | | 050-099 |
| 205R | 24 | | PL | E | 0-0 | 52-35-13 | D08072J | | 10 | | | | | 10 | | 050-099 |
| 301B | 20 | | PC | AA | 4-0 | 25-53-22 | C00036 | | A2 | D | | | | 1 | | 050-099 |
| 301B | 20 | | PC | AA | 4-0 | 25-53-22 | C00162 | | A2 | D | | | | 1 | | 150-199, 275-299 |
| 301R | 20 | | PC | AA | 0-0 | 25-53-22 | C00036 | | B2 | D | | | | 2 | | 050-099 |
| 301R | 20 | | PC | AA | 0-0 | 25-53-22 | C00162 | | B2 | D | | | | 2 | | 150-199, 275-299 |
| 301Y | 20 | | PC | AA | 0-0 | 25-53-22 | C00036 | | C2 | D | | | | 3 | | 050-099 |
| 301Y | 20 | | PC | AA | 0-0 | 25-53-22 | C00162 | | C2 | D | | | | 3 | | 150-199, 275-299 |
| 302B | 20 | | PC | AB | 4-0 | 25-53-22 | C00037 | | A2 | D | | | | 4 | | 050-099 |
| 302B | 20 | | PC | AB | 4-0 | 25-53-22 | C00159 | | A1 | D | | | | 4 | | 150-199, 275-299 |
| 302R | 20 | | PC | AB | 0-0 | 25-53-22 | C00037 | | B2 | D | | | | 5 | | 050-099 |
| 302R | 20 | | PC | AB | 0-0 | 25-53-22 | C00159 | | B1 | D | | | | 5 | | 150-199, 275-299 |
| 302Y | 20 | | PC | AB | 0-0 | 25-53-22 | C00037 | | C2 | D | | | | 6 | | 050-099 |
| 302Y | 20 | | PC | AB | 0-0 | 25-53-22 | C00159 | | C1 | D | | | | 6 | | 150-199, 275-299 |
| 303B | 20 | | PC | AC | 4-0 | 25-53-22 | C00038 | | A2 | D | | | | 7 | | 050-099 |
| 303R | 20 | | PC | AC | 0-0 | 25-53-22 | C00038 | | B2 | D | | | | 8 | | 050-099 |
| 303Y | 20 | | PC | AC | 0-0 | 25-53-22 | C00038 | | C2 | D | | | | 9 | | 050-099 |
| 304B | 20 | | PC | AD | 4-0 | 25-53-22 | C00039 | | A2 | D | | | | 11 | | 050-099 |
| 304B | 20 | | PC | AD | 4-0 | 25-53-22 | C00164 | | A2 | D | | | | 11 | | 150-199, 275-299 |
| 304R | 20 | | PC | AD | 0-0 | 25-53-22 | C00039 | | B2 | D | | | | 12 | | 050-099 |
| 304R | 20 | | PC | AD | 0-0 | 25-53-22 | C00164 | | B2 | D | | | | 12 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 65

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|-------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | |
| 304Y | 20 | PC | AD | | 0-0 | 25-53-22 | C00039 | C2 | D | | D05254J | 13 | | | 050-099 |
| 304Y | 20 | PC | AD | | 0-0 | 25-53-22 | C00164 | C2 | D | | D05254J | 13 | | | 150-199, 275-299 |
| 305B | 20 | PC | AE | | 4-0 | 25-53-22 | C00040 | A1 | D | | D05256J | 1 | | | 050-099 |
| 305B | 20 | PC | AE | | 4-0 | 25-53-22 | C00158 | A1 | D | | D05256J | 1 | | | 150-199, 275-299 |
| 305R | 20 | PC | AE | | 0-0 | 25-53-22 | C00040 | B1 | D | | D05256J | 2 | | | 050-099 |
| 305R | 20 | PC | AE | | 0-0 | 25-53-22 | C00158 | B1 | D | | D05256J | 2 | | | 150-199, 275-299 |
| 305Y | 20 | PC | AE | | 0-0 | 25-53-22 | C00040 | C1 | D | | D05256J | 3 | | | 050-099 |
| 305Y | 20 | PC | AE | | 0-0 | 25-53-22 | C00158 | C1 | D | | D05256J | 3 | | | 150-199, 275-299 |
| 306B | 20 | PC | AF | | 4-0 | 25-53-22 | C00041 | A1 | D | | D05256J | 4 | | | 050-099 |
| 306B | 20 | PC | AF | | 4-0 | 25-53-22 | C00163 | A2 | D | | D05256J | 4 | | | 150-199, 275-299 |
| 306R | 20 | PC | AF | | 0-0 | 25-53-22 | C00041 | B1 | D | | D05256J | 5 | | | 050-099 |
| 306R | 20 | PC | AF | | 0-0 | 25-53-22 | C00163 | B2 | D | | D05256J | 5 | | | 150-199, 275-299 |
| 306Y | 20 | PC | AF | | 0-0 | 25-53-22 | C00041 | C1 | D | | D05256J | 6 | | | 050-099 |
| 306Y | 20 | PC | AF | | 0-0 | 25-53-22 | C00163 | C2 | D | | D05256J | 6 | | | 150-199, 275-299 |
| 307B | 20 | PC | AG | | 4-0 | 25-53-22 | C00042 | A1 | D | | D05256J | 7 | | | 050-099 |
| 307B | 20 | PC | AG | | 4-0 | 25-53-22 | C00160 | A1 | D | | D05256J | 7 | | | 150-199, 275-299 |
| 307R | 20 | PC | AG | | 0-0 | 25-53-22 | C00042 | B1 | D | | D05256J | 8 | | | 050-099 |
| 307R | 20 | PC | AG | | 0-0 | 25-53-22 | C00160 | B1 | D | | D05256J | 8 | | | 150-199, 275-299 |
| 307Y | 20 | PC | AG | | 0-0 | 25-53-22 | C00042 | C1 | D | | D05256J | 9 | | | 050-099 |
| 307Y | 20 | PC | AG | | 0-0 | 25-53-22 | C00160 | C1 | D | | D05256J | 9 | | | 150-199, 275-299 |
| 308B | 20 | PC | AH | | 4-0 | 25-53-22 | C00043 | A1 | D | | D05256J | 11 | | | 050-099 |
| 308R | 20 | PC | AH | | 0-0 | 25-53-22 | C00043 | B1 | D | | D05256J | 12 | | | 050-099 |
| 308Y | 20 | PC | AH | | 0-0 | 25-53-22 | C00043 | C1 | D | | D05256J | 13 | | | 050-099 |
| 310B | 20 | PC | MJ | | 3-0 | 23-41-11 | SM00002 | | S | | D08072J | 14 | | | ALL |
| 310R | 20 | PC | MJ | | 0-0 | 23-41-11 | SM00001 | | S | | D08072J | 13 | | | ALL |
| 310Y | 20 | PC | MJ | | 0-0 | 23-41-11 | SM00003 | | S | | D08072J | 15 | | | ALL |
| 32A | 20 | PA | | | 5-0 | 25-53-21 | C00011 | | 2 D | | TB0120G | 15 | 2 | | 150-199, 275-299 |
| 32B | 22 | PA | | | 5-0 | 25-53-24 | C00011 | | 1 D | | TB0118Z | 21 | BJ | | 150-199, 275-299 |
| 32C | 22 | PA | | | 6-0 | 25-53-23 | TB0118Z | | 21 BJ | | S00680 | 4 | B | * | 150-199, 275-299 |
| 32D | 22 | PA | | | 2-0 | 25-53-23 | S00680 | | 2 B | * | L00819 | =G | \$ | | 150-199, 275-299 |
| 32E | 22 | PA | | | 6-0 | 25-53-23 | TB0118Z | | 10 BJ | | S00683 | 1 | B | | 150-199, 275-299 |
| 32F | 22 | PA | | | 6-0 | 25-53-23 | TB0118Z | | 21 BJ | | L00819 | =P | \$ | * | 150-199, 275-299 |
| 32G | 22 | PA | | | 2-0 | 25-53-23 | S00680 | | 4 B | * | S00681 | 4 | B | | 150-199, 275-299 |
| 32H | 22 | PA | | | 2-0 | 25-53-23 | S00680 | | 5 B | * | S00681 | 5 | B | * | 150-199, 275-299 |
| 32J | 22 | PA | | | 2-0 | 25-53-23 | S00681 | | 2 B | * | S00680 | 1 | B | | 150-199, 275-299 |
| 32K | 22 | PA | | | 2-0 | 25-53-23 | S00681 | | 2 B | * | L00820 | =G | \$ | | 150-199, 275-299 |
| 32L | 22 | PA | | | 2-0 | 25-53-23 | S00681 | | 5 B | * | S00682 | 5 | B | * | 150-199, 275-299 |
| 32M | 22 | PA | | | 2-0 | 25-53-23 | L00821 | | =P \$ | * | L00820 | =P | \$ | * | 150-199, 275-299 |
| 32P | 22 | PA | | | 2-0 | 25-53-23 | S00681 | | 1 B | | S00682 | 2 | B | * | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 66

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | |
| 32R | 22 | | PA | 2-0 | 25-53-23 | S00682 | 2 | B | * | L00821 | =G | \$ | | 150-199, 275-299 | | |
| 32T | 22 | | PA | 2-0 | 25-53-23 | S00682 | 5 | B | * | S00683 | 5 | B | | 150-199, 275-299 | | |
| 32W | 22 | | PA | 2-0 | 25-53-23 | L00822 | =P | \$ | * | L00821 | =P | \$ | * | 150-199, 275-299 | | |
| 32X | 22 | | PA | 2-0 | 25-53-23 | S00682 | 4 | B | * | S00683 | 4 | B | | 150-199, 275-299 | | |
| 32Y | 22 | | PA | 2-0 | 25-53-23 | S00682 | 1 | B | | S00683 | 2 | B | * | 150-199, 275-299 | | |
| 33A | 22 | | PA | 2-0 | 25-53-23 | S00683 | 2 | B | * | L00822 | =G | \$ | | 150-199, 275-299 | | |
| 33B | 22 | | PA | 2-0 | 25-53-23 | L00823 | =P | \$ | * | L00822 | =P | \$ | * | 150-199, 275-299 | | |
| 33C | 22 | | PA | 5-0 | 25-53-23 | S00680 | 5 | B | * | TB0118Z | 39 | BJ | | 150-199, 275-299 | | |
| 33D | 22 | | PA | 1-0 | 25-53-23 | D11180 | 3 | | | TB0118Z | 10 | BJ | | 150-199, 275-299 | | |
| 33E | 22 | | PA | 6-0 | 25-53-23 | S00680 | 2 | B | * | TB0122D | C002 | 2 | | 150-199, 275-299 | | |
| 33F | 22 | | PA | 1-0 | 25-53-23 | TB0122D | C002 | 2 | | TB0122D | C003 | 2 | | 150-199, 275-299 | | |
| 33G | 22 | | PA | 5-0 | 25-53-23 | S00681 | 2 | B | * | TB0122D | C004 | 2 | | 150-199, 275-299 | | |
| 33H | 22 | | PA | 1-0 | 25-53-23 | TB0122D | C004 | 2 | | TB0122D | C005 | 2 | | 150-199, 275-299 | | |
| 33J | 22 | | PA | 5-0 | 25-53-23 | S00682 | 2 | B | * | TB0122D | C006 | 2 | | 150-199, 275-299 | | |
| 33K | 22 | | PA | 1-0 | 25-53-23 | TB0122D | C006 | 2 | | TB0122D | C007 | 2 | | 150-199, 275-299 | | |
| 33L | 22 | | PA | 3-0 | 25-53-23 | D11192 | 7 | | | TB0118Z | 4 | BJ | | 150-199, 275-299 | | |
| 33M | 22 | | PA | 3-0 | 25-53-23 | D11192 | 3 | | | TB0122D | A008 | 2 | | 150-199, 275-299 | | |
| 33N | 22 | | PA | 3-0 | 25-53-23 | D11190 | 7 | | | TB0118Z | 3 | BJ | | 150-199, 275-299 | | |
| 33P | 22 | | PA | 3-0 | 25-53-23 | D11190 | 3 | | | TB0122D | A009 | 2 | | 150-199, 275-299 | | |
| 33R | 22 | | PA | 1-0 | 25-53-23 | TB0122D | C008 | 2 | | TB0122D | C009 | 2 | | 150-199, 275-299 | | |
| 33T | 22 | | PA | 1-0 | 25-53-23 | TB0118Z | 10 | BJ | | TB0118Z | 11 | BJ | | 150-199, 275-299 | | |
| 33W | 22 | | PA | 6-0 | 25-53-23 | TB0118G | 31 | 2 | | S00682 | 4 | B | * | 150-199, 275-299 | | |
| 33X | 22 | | PA | 2-0 | 25-53-23 | L00825 | =P | \$ | * | L00823 | =P | \$ | * | 150-199, 275-299 | | |
| 33Y | 22 | | PA | 2-0 | 25-53-23 | L00824 | =P | \$ | | L00825 | =P | \$ | * | 150-199, 275-299 | | |
| 340B | 20 | | PC | AI | 4-0 | 25-53-22 | C00161 | A1 | D | D05256J | 11 | | | 150-199, 275-299 | | |
| 340R | 20 | | PC | AI | 0-0 | 25-53-22 | C00161 | B1 | D | D05256J | 12 | | | 150-199, 275-299 | | |
| 340Y | 20 | | PC | AI | 0-0 | 25-53-22 | C00161 | C1 | D | D05256J | 13 | | | 150-199, 275-299 | | |
| 341B | 20 | | PC | AJ | 4-0 | 25-53-22 | C00165 | A2 | D | D05254J | 7 | | | 150-199, 275-299 | | |
| 341R | 20 | | PC | AJ | 0-0 | 25-53-22 | C00165 | B2 | D | D05254J | 8 | | | 150-199, 275-299 | | |
| 341Y | 20 | | PC | AJ | 0-0 | 25-53-22 | C00165 | C2 | D | D05254J | 9 | | | 150-199, 275-299 | | |
| 34A | 22 | | PA | | 6-0 | 25-53-23 | TB0118Z | 11 | BJ | L00823 | =G | \$ | | 150-199, 275-299 | | |
| 34B | 22 | | PA | | 3-0 | 25-53-23 | D11196 | 7 | | TB0118Z | 4 | BJ | | 150-199, 275-299 | | |
| 34D | 22 | | PA | | 4-0 | 25-53-23 | D11206 | 3 | | TB0118Z | 12 | BJ | | 150-199, 275-299 | | |
| 34E | 22 | | PA | | 3-0 | 25-53-23 | D11194 | 7 | | TB0118Z | 3 | BJ | | 150-199, 275-299 | | |
| 34F | 22 | | PA | | 4-0 | 25-53-24 | D11186 | 8 | | D05258J | 40 | | | 150-199, 275-299 | | |
| 34G | 22 | | PA | | 4-0 | 25-53-23 | D11204 | 3 | | TB0118Z | 12 | BJ | | 150-199, 275-299 | | |
| 34H | 22 | | PA | | 1-0 | 25-53-23 | D11188 | 3 | | TB0118Z | 12 | BJ | | 150-199, 275-299 | | |
| 34J | 22 | | PA | | 2-0 | 25-53-23 | D11186 | 3 | | TB0118Z | 40 | BJ | | 150-199, 275-299 | | |
| 34K | 22 | | PA | | 2-0 | 25-53-23 | D11184 | 3 | | TB0118Z | 40 | BJ | | 150-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 67

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | |
| 34L | 22 | | PA | 6-0 | 25-53-23 | L00825 | = G | \$ | | | | TB0118Z | 12 | BJ | | 150-199, 275-299 |
| 34M | 22 | | PA | 3-0 | 25-53-23 | D02544 | | 11 | | | | TB0118Z | 42 | BJ | | 150-199, 275-299 |
| 34P | 22 | | PA | 5-0 | 25-53-23 | L00824 | = G | \$ | | | | TB0118Z | 42 | BJ | | 150-199, 275-299 |
| 34R | 22 | | PA | 3-0 | 25-53-24 | D01784 | | B2 | | | | TB0118Z | 21 | BJ | | 150-199, 275-299 |
| 34T | 22 | | PA | 3-0 | 25-53-24 | D01786 | | B2 | | | | TB0118Z | 21 | BJ | | 150-199, 275-299 |
| 34W | 22 | | PA | 3-0 | 25-53-24 | D11182 | | 2 | | | | TB0118Z | 16 | BJ | | 150-199, 275-299 |
| 34X | 22 | | PA | 3-0 | 25-53-24 | D11182 | | 7 | | | | TB0118Z | 16 | BJ | | 150-199, 275-299 |
| 34Y | 22 | | PA | 3-0 | 25-53-24 | D11182 | | 5 | | | | TB0118G | 5 | 2 | | 150-199, 275-299 |
| 35A | 22 | | PA | 3-0 | 25-53-24 | D11196 | | 6 | | | | TB0118G | 5 | 2 | | 150-199, 275-299 |
| 35B | 22 | | PA | 3-0 | 25-53-24 | D11196 | | 2 | | | | TB0118Z | 13 | BJ | | 150-199, 275-299 |
| 35D | 22 | | PA | 1-0 | 25-53-24 | D11180 | | 7 | | | | TB0118Z | 13 | BJ | | 150-199, 275-299 |
| 35E | 22 | | PA | 1-0 | 25-53-24 | D02588 | | 2 | | | | TB0118Z | 20 | BJ | | 150-199, 275-299 |
| 35F | 22 | | PA | 1-0 | 25-53-24 | D02588 | | 7 | | | | TB0118Z | 20 | BJ | | 150-199, 275-299 |
| 35G | 22 | | PA | 1-0 | 25-53-24 | D02588 | | 5 | | | | TB0118Z | 13 | BJ | | 150-199, 275-299 |
| 35H | 22 | | PA | 3-0 | 25-53-24 | D11194 | | 6 | | | | TB0118G | 5 | 2 | | 150-199, 275-299 |
| 35J | 22 | | PA | 3-0 | 25-53-24 | D11194 | | 2 | | | | TB0118Z | 13 | BJ | | 150-199, 275-299 |
| 35K | 22 | | PA | 1-0 | 25-53-24 | D02578 | | 2 | | | | TB0118Z | 14 | BJ | | 150-199, 275-299 |
| 35L | 22 | | PA | 1-0 | 25-53-24 | D02578 | | 7 | | | | TB0118Z | 14 | BJ | | 150-199, 275-299 |
| 35M | 22 | | PA | 2-0 | 25-53-24 | D02578 | | 5 | | | | TB0118G | 37 | 2 | | 150-199, 275-299 |
| 35N | 22 | | PA | 2-0 | 25-53-24 | D11190 | | 6 | | | | TB0118G | 37 | 2 | | 150-199, 275-299 |
| 35P | 22 | | PA | 2-0 | 25-53-24 | D11190 | | 2 | | | | TB0118G | 38 | 2 | | 150-199, 275-299 |
| 35R | 22 | | PA | 1-0 | 25-53-24 | D11180 | | 2 | | | | TB0118Z | 18 | BJ | | 150-199, 275-299 |
| 35T | 22 | | PA | 2-0 | 25-53-24 | D11180 | | 5 | | | | TB0118G | 38 | 2 | | 150-199, 275-299 |
| 35W | 22 | | PA | 2-0 | 25-53-24 | D11192 | | 6 | | | | TB0118G | 37 | 2 | | 150-199, 275-299 |
| 35X | 22 | | PA | 2-0 | 25-53-24 | D11192 | | 2 | | | | TB0118G | 38 | 2 | | 150-199, 275-299 |
| 35Y | 22 | | PA | 3-0 | 25-53-24 | D11196 | | 1 | | | | D05258J | 3 | | | 150-199, 275-299 |
| 36A | 22 | | PA | 3-0 | 25-53-24 | D11196 | | 5 | | | | D05258J | 6 | | | 150-199, 275-299 |
| 36B | 22 | | PA | 3-0 | 25-53-24 | D11194 | | 1 | | | | D05258J | 9 | | | 150-199, 275-299 |
| 36C | 22 | | PA | 3-0 | 25-53-24 | D11194 | | 5 | | | | D05258J | 13 | | | 150-199, 275-299 |
| 36D | 22 | | PA | 3-0 | 25-53-24 | D11190 | | 1 | | | | D05258J | 16 | | | 150-199, 275-299 |
| 36E | 22 | | PA | 3-0 | 25-53-24 | D11190 | | 5 | | | | D05258J | 19 | | | 150-199, 275-299 |
| 36F | 22 | | PA | 3-0 | 25-53-24 | D11192 | | 1 | | | | D05258J | 29 | | | 150-199, 275-299 |
| 36G | 22 | | PA | 3-0 | 25-53-24 | D11192 | | 5 | | | | D05258J | 33 | | | 150-199, 275-299 |
| 36H | 22 | | PA | 2-0 | 25-53-24 | D11184 | | 6 | | | | TB0118G | 43 | 2 | | 150-199, 275-299 |
| 36J | 22 | | PA | 1-0 | 25-53-24 | D11186 | | 6 | | | | D11184 | 8 | | | 150-199, 275-299 |
| 37A | 22 | | PA | 7-0 | 25-53-25 | D02558 | | D3 | | | | TB0308Y | A001 | BJ | | 050-099 |
| 37A | 22 | | PA | 6-0 | 25-53-25 | D02558 | | D3 | | | | TB0308Y | A001 | BJ | | 150-199, 275-299 |
| 37B | 22 | | PA | 5-0 | 25-53-25 | D02558 | | D2 | | | | TB0122H | 3 | 2 | | 050-099 |
| 37B | 22 | | PA | 3-0 | 25-53-25 | D02558 | | D2 | | | | TB0118Z | 33 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 68

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | |
| 37C | 22 | | PA | 7-0 | 25-53-25 | D02558 | | D1 | | | | TB0308Y | A002 | BJ | | 050-099 |
| 37C | 22 | | PA | 6-0 | 25-53-25 | D02558 | | D1 | | | | TB0308Y | A002 | BJ | | 150-199, 275-299 |
| 37D | 22 | | PA | 7-0 | 25-53-25 | D02560 | | D3 | | | | TB0308Y | A003 | BJ | | 050-099 |
| 37D | 22 | | PA | 6-0 | 25-53-25 | D02560 | | D3 | | | | TB0308Y | A003 | BJ | | 150-199, 275-299 |
| 37E | 22 | | PA | 5-0 | 25-53-25 | D02560 | | D2 | | | | TB0122H | 3 | 2 | | 050-099 |
| 37E | 22 | | PA | 3-0 | 25-53-25 | D02560 | | D2 | | | | TB0118Z | 33 | BJ | | 150-199, 275-299 |
| 37F | 22 | | PA | 7-0 | 25-53-25 | D02560 | | D1 | | | | TB0308Y | A004 | BJ | | 050-099 |
| 37F | 22 | | PA | 6-0 | 25-53-25 | D02560 | | D1 | | | | TB0308Y | A004 | BJ | | 150-199, 275-299 |
| 37G | 22 | | PA | 4-0 | 25-53-26 | D05250J | | 6 | | | | TB0118Y | A055 | BJ | | 050-099 |
| 37G | 22 | | PA | 5-0 | 25-53-26 | D05250J | | 6 | | | | TB0118Z | 15 | BJ | | 150-199, 275-299 |
| 37H | 22 | | PA | 4-0 | 25-53-26 | D05250J | | 22 | | | | D11668 | 6 | | | ALL |
| 37J | 22 | | PA | 4-0 | 25-53-26 | D05250J | | 5 | | | | TB0308Z | 13 | BJ | | 050-099 |
| 37J | 22 | | PA | 3-0 | 25-53-26 | D05250J | | 5 | | | | TB0118Z | 52 | BJ | | 150-199, 275-299 |
| 37K | 22 | | PA | 6-0 | 25-53-26 | D02554 | | X1 | | | | TB0308Y | C001 | BJ | | 050-099 |
| 37K | 22 | | PA | 3-0 | 25-53-26 | D02554 | | X1 | | | | TB0118G | 55 | 2 | | 150-199, 275-299 |
| 37L | 22 | | PA | 7-0 | 25-53-26 | D02556 | | X1 | | | | TB0308Z | 13 | BJ | | 050-099 |
| 37L | 22 | | PA | 3-0 | 25-53-26 | D02556 | | X1 | | | | TB0118Z | 52 | BJ | | 150-199, 275-299 |
| 37M | 22 | | PA | 4-0 | 25-53-27 | D05250J | | 24 | | | | TB0308Y | C004 | BJ | | 050-099 |
| 37M | 22 | | PA | 5-0 | 25-53-27 | D05250J | | 24 | | | | TB0308Y | C004 | BJ | | 150-199 |
| 37N | 22 | | PA | 4-0 | 25-53-27 | D05250J | | 23 | | | | TB0308Y | C005 | BJ | | 050-099 |
| 37N | 22 | | PA | 5-0 | 25-53-27 | D05250J | | 23 | | | | TB0308Y | C005 | BJ | | 150-199 |
| 37P | 22 | | PA | 4-0 | 25-53-27 | D05250J | | 8 | | | | TB0308Y | C006 | BJ | | 050-099 |
| 37P | 22 | | PA | 5-0 | 25-53-27 | D05250J | | 8 | | | | TB0308Y | C006 | BJ | | 150-199 |
| 37R | 22 | | PA | 6-0 | 25-53-27 | D02564 | | X1 | | | | TB0308Y | C006 | BJ | | 050-099 |
| 37R | 22 | | PA | 7-0 | 25-53-27 | D02564 | | X1 | | | | TB0308Y | C006 | BJ | | 150-199 |
| 37T | 22 | | PA | 4-0 | 25-53-23 | TB0122H | | 5 | 2 | | | TB0308Z | 8 | BJ | | 050-099 |
| 37T | 22 | | PA | 6-0 | 25-53-23 | TB0118Z | | 40 | BJ | | | TB0308Z | 8 | BJ | | 150-199, 275-299 |
| 37U | 22 | | PA | 1-0 | 25-53-23 | TB0308Z | | 9 | BJ | | | TB0308Z | 8 | BJ | | ALL |
| 37V | 22 | | PA | 5-0 | 25-53-26 | TB0308Z | | 11 | BJ | | | TB0122H | 3 | 2 | | 050-099 |
| 37V | 22 | | PA | 6-0 | 25-53-26 | TB0308Z | | 11 | BJ | | | TB0118Z | 33 | BJ | | 150-199, 275-299 |
| 38A | 22 | | PA | 7-0 | 25-53-25 | D10628 | | A1 | | | | TB0120H | 7 | 2 | | ALL |
| 38B | 22 | | PA | 8-0 | 25-53-25 | D10628 | | A2 | | | | C00046 | 1 | D | | 050-099 |
| 38B | 22 | | PA | 7-0 | 25-53-25 | D10628 | | A2 | | | | C00046 | 1 | D | | 150-199, 275-299 |
| 38D | 22 | | PA | 3-0 | 25-53-25 | D10628 | | X1 | | | | TB0308Z | 7 | BJ | | 050-099 |
| 38D | 22 | | PA | 2-0 | 25-53-25 | D10628 | | X1 | | | | TB0308Z | 7 | BJ | | 150-199, 275-299 |
| 38E | 22 | | PA | 3-0 | 25-53-25 | D10628 | | X2 | | | | TB0308Z | 8 | BJ | | 050-099 |
| 38E | 22 | | PA | 2-0 | 25-53-25 | D10628 | | X2 | | | | TB0308Z | 8 | BJ | | 150-199, 275-299 |
| 39A | 22 | | PA | 7-0 | 25-53-26 | D10636 | | A1 | | | | TB0120H | 1 | 2 | | ALL |
| 39B | 22 | | PA | 8-0 | 25-53-26 | D10636 | | A2 | | | | C00050 | 1 | D | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 69

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | | | |
| 39B | 22 | | PA | 7-0 | 25-53-26 | D10636 | | A2 | | | | | | C00080 | 1 | D | | 275-299 |
| 39D | 22 | | PA | 3-0 | 25-53-26 | D10636 | | X1 | | | | | | TB0308Z | 10 | BJ | | 050-099 |
| 39D | 22 | | PA | 2-0 | 25-53-26 | D10636 | | X1 | | | | | | TB0308Z | 10 | BJ | | 150-199, 275-299 |
| 39E | 22 | | PA | 3-0 | 25-53-26 | D10636 | | X2 | | | | | | TB0308Z | 9 | BJ | | 050-099 |
| 39E | 22 | | PA | 2-0 | 25-53-26 | D10636 | | X2 | | | | | | TB0308Z | 9 | BJ | | 150-199, 275-299 |
| 40A | 22 | | PA | 4-0 | 25-53-23 | S00683 | | | | B | * | | | TB0122D | C009 | 2 | | 150-199, 275-299 |
| 40B | 22 | | PA | 3-0 | 25-53-25 | D10620 | | 2 | | | | | | TB0308Z | 12 | BJ | | 050-099 |
| 40B | 22 | | PA | 2-0 | 25-53-25 | D10620 | | 2 | | | | | | TB0308Z | 12 | BJ | | 150-199, 275-299 |
| 40C | 22 | | PA | 3-0 | 25-53-25 | D10620 | | 3 | | | | | | TB0308Z | 8 | BJ | | 050-099 |
| 40C | 22 | | PA | 2-0 | 25-53-25 | D10620 | | 3 | | | | | | TB0308Z | 8 | BJ | | 150-199, 275-299 |
| 40E | 22 | | PA | 3-0 | 25-53-25 | D10620 | | 5 | | | | | | TB0308Z | 7 | BJ | | 050-099 |
| 40E | 22 | | PA | 2-0 | 25-53-25 | D10620 | | 5 | | | | | | TB0308Z | 7 | BJ | | 150-199, 275-299 |
| 40G | 22 | | PA | 3-0 | 25-53-25 | D10620 | | 7 | | | | | | TB0308Y | A001 | BJ | | 050-099 |
| 40G | 22 | | PA | 2-0 | 25-53-25 | D10620 | | 7 | | | | | | TB0308Y | A001 | BJ | | 150-199, 275-299 |
| 41B | 22 | | PA | 3-0 | 25-53-25 | D10622 | | 2 | | | | | | TB0308Z | 12 | BJ | | 050-099 |
| 41B | 22 | | PA | 2-0 | 25-53-25 | D10622 | | 2 | | | | | | TB0308Z | 12 | BJ | | 150-199, 275-299 |
| 41C | 22 | | PA | 3-0 | 25-53-25 | D10622 | | 3 | | | | | | TB0308Z | 8 | BJ | | 050-099 |
| 41C | 22 | | PA | 2-0 | 25-53-25 | D10622 | | 3 | | | | | | TB0308Z | 8 | BJ | | 150-199, 275-299 |
| 41E | 22 | | PA | 3-0 | 25-53-25 | D10622 | | 5 | | | | | | TB0308Z | 7 | BJ | | 050-099 |
| 41E | 22 | | PA | 2-0 | 25-53-25 | D10622 | | 5 | | | | | | TB0308Z | 7 | BJ | | 150-199, 275-299 |
| 41G | 22 | | PA | 3-0 | 25-53-25 | D10622 | | 7 | | | | | | TB0308Y | A002 | BJ | | 050-099 |
| 41G | 22 | | PA | 2-0 | 25-53-25 | D10622 | | 7 | | | | | | TB0308Y | A002 | BJ | | 150-199, 275-299 |
| 42B | 22 | | PA | 3-0 | 25-53-25 | D10624 | | 2 | | | | | | TB0308Z | 12 | BJ | | 050-099 |
| 42B | 22 | | PA | 2-0 | 25-53-25 | D10624 | | 2 | | | | | | TB0308Z | 12 | BJ | | 150-199, 275-299 |
| 42C | 22 | | PA | 3-0 | 25-53-25 | D10624 | | 3 | | | | | | TB0308Z | 8 | BJ | | 050-099 |
| 42C | 22 | | PA | 2-0 | 25-53-25 | D10624 | | 3 | | | | | | TB0308Z | 8 | BJ | | 150-199, 275-299 |
| 42E | 22 | | PA | 3-0 | 25-53-25 | D10624 | | 5 | | | | | | TB0308Z | 7 | BJ | | 050-099 |
| 42E | 22 | | PA | 2-0 | 25-53-25 | D10624 | | 5 | | | | | | TB0308Z | 7 | BJ | | 150-199, 275-299 |
| 42G | 22 | | PA | 3-0 | 25-53-25 | D10624 | | 7 | | | | | | TB0308Y | A003 | BJ | | 050-099 |
| 42G | 22 | | PA | 2-0 | 25-53-25 | D10624 | | 7 | | | | | | TB0308Y | A003 | BJ | | 150-199, 275-299 |
| 43B | 22 | | PA | 3-0 | 25-53-25 | D10626 | | 2 | | | | | | TB0308Z | 12 | BJ | | 050-099 |
| 43B | 22 | | PA | 2-0 | 25-53-25 | D10626 | | 2 | | | | | | TB0308Z | 12 | BJ | | 150-199, 275-299 |
| 43C | 22 | | PA | 3-0 | 25-53-25 | D10626 | | 3 | | | | | | TB0308Z | 8 | BJ | | 050-099 |
| 43C | 22 | | PA | 2-0 | 25-53-25 | D10626 | | 3 | | | | | | TB0308Z | 8 | BJ | | 150-199, 275-299 |
| 43E | 22 | | PA | 3-0 | 25-53-25 | D10626 | | 5 | | | | | | TB0308Z | 7 | BJ | | 050-099 |
| 43E | 22 | | PA | 2-0 | 25-53-25 | D10626 | | 5 | | | | | | TB0308Z | 7 | BJ | | 150-199, 275-299 |
| 43G | 22 | | PA | 3-0 | 25-53-25 | D10626 | | 7 | | | | | | TB0308Y | A004 | BJ | | 050-099 |
| 43G | 22 | | PA | 2-0 | 25-53-25 | D10626 | | 7 | | | | | | TB0308Y | A004 | BJ | | 150-199, 275-299 |
| 44B | 22 | | PA | 3-0 | 25-53-26 | D10630 | | 2 | | | | | | TB0308Z | 11 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 70

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | | |
| 44B | 22 | | PA | 2-0 | 25-53-26 | D10630 | | 2 | | | | | TB0308Z | 11 | BJ | | 150-199, 275-299 |
| 44C | 22 | | PA | 3-0 | 25-53-26 | D10630 | | 3 | | | | | TB0308Z | 9 | BJ | | 050-099 |
| 44C | 22 | | PA | 7-0 | 25-53-26 | D10630 | | 3 | | | | | TB0308Z | 9 | BJ | | 150-199, 275-299 |
| 44E | 22 | | PA | 3-0 | 25-53-26 | D10630 | | 5 | | | | | TB0308Z | 10 | BJ | | 050-099 |
| 44E | 22 | | PA | 2-0 | 25-53-26 | D10630 | | 5 | | | | | TB0308Z | 10 | BJ | | 150-199, 275-299 |
| 44G | 22 | | PA | 2-0 | 25-53-26 | D10630 | | 7 | | | | | TB0308Y | C001 | BJ | | 050-099 |
| 44G | 22 | | PA | 8-0 | 25-53-26 | D10630 | | 7 | | | | | TB0118G | 55 | 2 | | 150-199, 275-299 |
| 45B | 22 | | PA | 3-0 | 25-53-26 | D10632 | | 2 | | | | | TB0308Z | 11 | BJ | | 050-099 |
| 45B | 22 | | PA | 2-0 | 25-53-26 | D10632 | | 2 | | | | | TB0308Z | 11 | BJ | | 150-199, 275-299 |
| 45C | 22 | | PA | 3-0 | 25-53-26 | D10632 | | 3 | | | | | TB0308Z | 9 | BJ | | 050-099 |
| 45C | 22 | | PA | 2-0 | 25-53-26 | D10632 | | 3 | | | | | TB0308Z | 9 | BJ | | 150-199, 275-299 |
| 45E | 22 | | PA | 3-0 | 25-53-26 | D10632 | | 5 | | | | | TB0308Z | 10 | BJ | | 050-099 |
| 45E | 22 | | PA | 2-0 | 25-53-26 | D10632 | | 5 | | | | | TB0308Z | 10 | BJ | | 150-199, 275-299 |
| 45G | 22 | | PA | 5-0 | 25-53-26 | D10632 | | 7 | | | | | D11668 | 8 | | | 050-099 |
| 45G | 22 | | PA | 2-0 | 25-53-26 | D10632 | | 7 | | | | | TB0308Y | C002 | BJ | | 150-199, 275-299 |
| 46B | 22 | | PA | 3-0 | 25-53-26 | D10634 | | 2 | | | | | TB0308Z | 11 | BJ | | 050-099 |
| 46B | 22 | | PA | 2-0 | 25-53-26 | D10634 | | 2 | | | | | TB0308Z | 11 | BJ | | 150-199, 275-299 |
| 46C | 22 | | PA | 3-0 | 25-53-26 | D10634 | | 3 | | | | | TB0308Z | 9 | BJ | | 050-099 |
| 46C | 22 | | PA | 2-0 | 25-53-26 | D10634 | | 3 | | | | | TB0308Z | 9 | BJ | | 150-199, 275-299 |
| 46E | 22 | | PA | 3-0 | 25-53-26 | D10634 | | 5 | | | | | TB0308Z | 10 | BJ | | 050-099 |
| 46E | 22 | | PA | 2-0 | 25-53-26 | D10634 | | 5 | | | | | TB0308Z | 10 | BJ | | 150-199, 275-299 |
| 46G | 22 | | PA | 2-0 | 25-53-26 | D10634 | | 7 | | | | | TB0308Z | 13 | BJ | | 050-099 |
| 46G | 22 | | PA | 7-0 | 25-53-26 | D10634 | | 7 | | | | | TB0118Z | 52 | BJ | | 150-199, 275-299 |
| 47B | 22 | | PA | 3-0 | 25-53-27 | D10638 | | 2 | | | | | TB0308Z | 11 | BJ | | 050-099, 150-199 |
| 47C | 22 | | PA | 3-0 | 25-53-27 | D10638 | | 3 | | | | | TB0308Z | 9 | BJ | | 050-099, 150-199 |
| 47E | 22 | | PA | 3-0 | 25-53-27 | D10638 | | 5 | | | | | TB0308Z | 10 | BJ | | 050-099, 150-199 |
| 47G | 22 | | PA | 3-0 | 25-53-27 | D10638 | | 7 | | | | | TB0308Y | C004 | BJ | | 050-099, 150-199 |
| 48B | 22 | | PA | 3-0 | 25-53-27 | D10640 | | 2 | | | | | TB0308Z | 11 | BJ | | 050-099, 150-199 |
| 48C | 22 | | PA | 3-0 | 25-53-27 | D10640 | | 3 | | | | | TB0308Z | 9 | BJ | | 050-099, 150-199 |
| 48E | 22 | | PA | 3-0 | 25-53-27 | D10640 | | 5 | | | | | TB0308Z | 10 | BJ | | 050-099, 150-199 |
| 48G | 22 | | PA | 3-0 | 25-53-27 | D10640 | | 7 | | | | | TB0308Y | C005 | BJ | | 050-099, 150-199 |
| 49B | 22 | | PA | 3-0 | 25-53-27 | D10642 | | 2 | | | | | TB0308Z | 11 | BJ | | 050-099, 150-199 |
| 49C | 22 | | PA | 3-0 | 25-53-27 | D10642 | | 3 | | | | | TB0308Z | 9 | BJ | | 050-099, 150-199 |
| 49E | 22 | | PA | 3-0 | 25-53-27 | D10642 | | 5 | | | | | TB0308Z | 10 | BJ | | 050-099, 150-199 |
| 49G | 22 | | PA | 3-0 | 25-53-27 | D10642 | | 7 | | | | | TB0308Y | C006 | BJ | | 050-099, 150-199 |
| 501 | 22 | | PA | 3-0 | 25-53-21 | D05250J | | 1 | | | | | TB0122H | 3 | 2 | | 050-099 |
| 501 | 22 | | PA | 4-0 | 25-53-21 | D05250J | | 1 | | | | | TB0118Z | 33 | BJ | | 150-199, 275-299 |
| 502 | 20 | | PA | 5-0 | 25-53-21 | D05250J | | 2 | | | | | D02566 | 5 | | | 050-099 |
| 502 | 20 | | PA | 4-0 | 25-53-21 | D05250J | | 2 | | | | | D02566 | 5 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 71

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | | |
| 503 | 20 | | PA | 3-0 | 25-53-21 | D05250J | | 3 | | | | | TB0122H | 1 | 2 | | 050-099 |
| 503 | 20 | | PA | 5-0 | 25-53-21 | D05250J | | 3 | | | | | TB0118Z | 35 | BJ | | 150-199, 275-299 |
| 504 | 22 | | PA | 3-0 | 25-53-23 | D05250J | | 4 | | | | | TB0118Y | A052 | BJ | | 050-099 |
| 504 | 22 | | PA | 4-0 | 25-53-23 | D05250J | | 4 | | | | | TB0118Z | 17 | BJ | | 150-199, 275-299 |
| 507 | 22 | | PA | 5-0 | 25-53-27 | D05250J | | 7 | | | | | D02562 | X1 | | | 050-099 |
| 507 | 22 | | PA | 5-0 | 25-53-27 | D02562 | | X1 | | | | | D05250J | 7 | | | 150-199 |
| 511 | 22 | | PA | 4-0 | 25-53-21 | D05250J | | 11 | | | | | C00075 | 1 | D | * | 050-099 |
| 511 | 22 | | PA | 3-0 | 25-53-21 | D05250J | | 11 | | | | | C00075 | 1 | D | | 150-199, 275-299 |
| 513 | 22 | | PA | 3-0 | 25-53-23 | D05250J | | 13 | | | | | TB0118Y | C052 | BJ | | 050-099 |
| 513 | 22 | | PA | 4-0 | 25-53-23 | TB0118Z | | 34 | BJ | | | | D11198 | X1 | | | 150-199, 275-299 |
| 514 | 22 | | PA | 2-0 | 25-53-24 | TB0118Y | | C053 | BJ | | | | D01784 | X1 | | | 050-099 |
| 514 | 22 | | PA | 4-0 | 25-53-24 | D11208 | | 1 | | | | | D01784 | X1 | | | 150-199, 275-299 |
| 515 | 22 | | PA | 2-0 | 25-53-24 | TB0118Y | | A053 | BJ | | | | D01786 | X1 | | | 050-099 |
| 515 | 22 | | PA | 5-0 | 25-53-24 | D05250J | | 15 | | | | | TB0118Z | 8 | BJ | | 150-199, 275-299 |
| 516 | 22 | | PA | 5-0 | 25-53-23 | D05250J | | 16 | | | | | TB0118G | 1 | 2 | | ALL |
| 517 | 22 | | PA | 5-0 | 25-53-23 | D05250J | | 17 | | | | | TB0118G | 2 | 2 | | ALL |
| 518 | 22 | | PA | 5-0 | 25-53-25 | D05250J | | 18 | | | | | D02544 | 7 | | | 050-099 |
| 518 | 22 | | PA | 4-0 | 25-53-25 | TB0118G | | 7 | 2 | | | | D02544 | 7 | | | 150-199, 275-299 |
| 521 | 20 | | PA | 3-0 | 25-53-21 | D05616J | | 1 | | | | | TB0122H | 1 | 2 | | 050-099 |
| 521 | 20 | | PA | 4-0 | 25-53-21 | D05616J | | 1 | | | | | TB0118Z | 35 | BJ | | 150-199, 275-299 |
| 522 | 20 | | PA | 2-0 | 25-53-21 | D05616J | | 2 | | | | | TB0122D | C | 2 | | 050-099 |
| 522 | 20 | | PA | 2-0 | 25-53-21 | D05616J | | 2 | | | | | TB0122D | C001 | 2 | | 150-199, 275-299 |
| 523 | 24 | | PK | 3-0 | 52-35-12 | D05616J | | 3 | | | | | TB0122G | 7 | 2 | | 050-099 |
| 523 | 24 | | PK | 3-0 | 52-35-12 | D05616J | | 3 | | | | | TB0118G | 50 | 2 | | 150-199, 275-299 |
| 524 | 24 | | PK | 4-0 | 52-35-12 | D05616J | | 4 | | | | | D02516 | X2 | | | ALL |
| 525 | 24 | | PK | 4-0 | 52-35-12 | D05616J | | 5 | | | | | D02518 | X2 | | | ALL |
| 526 | 24 | | PK | 3-0 | 52-35-12 | D05616J | | 6 | | | | | D05888J | 6 | | | 050-099 |
| 526 | 24 | | PK | 2-0 | 52-35-12 | D05616J | | 6 | | | | | D05888J | 6 | | | 150-199, 275-299 |
| 527 | 24 | | PK | 2-0 | 52-35-12 | D05616J | | 7 | | | | | R00037 | C | 2 | | 050-099 |
| 527 | 24 | | PK | 2-0 | 52-35-12 | D05616J | | 7 | | | | | TB0122D | C010 | 2 | | 150-199, 275-299 |
| 528 | 24 | | PK | 4-0 | 52-35-12 | D05616J | | 8 | | | | | D02512 | X2 | | | ALL |
| 529 | 24 | | PK | 4-0 | 52-35-12 | D05616J | | 9 | | | | | D02514 | X2 | | | ALL |
| 530 | 22 | | PA | 3-0 | 25-53-23 | D05616J | | 10 | | | | | TB0122H | 5 | 2 | | 050-099 |
| 530 | 22 | | PA | 4-0 | 25-53-23 | D05616J | | 10 | | | | | TB0118Z | 40 | BJ | | 150-199, 275-299 |
| 531 | 22 | | PA | 4-0 | 25-53-23 | TB0118H | | 39 | 2 | | | | TB0122H | 5 | 2 | | 050-099 |
| 531 | 22 | | PA | 1-0 | 25-53-23 | TB0118Z | | 39 | BJ | | | | TB0118Z | 40 | BJ | | 150-199, 275-299 |
| 532 | 22 | | PA | 5-0 | 25-53-23 | TB0120H | | 5 | 2 | | | | TB0122H | 5 | 2 | | 050-099 |
| 532 | 22 | | PA | 1-0 | 25-53-23 | TB0118Z | | 40 | BJ | | | | TB0118Z | 41 | BJ | | 150-199, 275-299 |
| 535 | 22 | | PA | 4-0 | 25-53-24 | D05616J | | 15 | | | | | TB0118H | 43 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 72

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | | | |
| 535 | 22 | | PA | 4-0 | 25-53-24 | D05616J | | 15 | | | | | | TB0118G | 43 | 2 | | 150-199, 275-299 |
| 537 | 20 | | PA | 6-0 | 33-37-21 | D02630 | | X1 | | | | | | TB0122H | 1 | 2 | | 050-099 |
| 537 | 20 | | PA | 4-0 | 33-37-21 | D02630 | | X1 | | | | | | TB0118Z | 35 | BJ | | 150-199, 275-299 |
| 538 | 20 | | PA | 4-0 | 33-37-21 | D02630 | | X2 | | | | | | D05616J | 17 | | | ALL |
| 540 | 22 | | PA | 6-0 | 25-53-23 | S00392 | | 10 | C | | * | | | TB0118D | C037 | 2 | | 050-099 |
| 541 | 22 | | PA | 3-0 | 25-53-23 | S00392 | | 1 | C | | | | | L00159 | =P | \$ | | 050-099 |
| 542 | 22 | | PA | 6-0 | 25-53-21 | S00392 | | 2 | C | | | | | TB0122H | 3 | 2 | | 050-099 |
| 543 | 22 | | PA | 1-0 | 25-53-23 | S00392 | | 3 | C | | | | | S00392 | 5 | C | | 050-099 |
| 544 | 22 | | PA | 3-0 | 25-53-23 | S00392 | | 4 | C | | | | | L00157 | =P | \$ | | 050-099 |
| 545 | 22 | | PA | 7-0 | 25-53-23 | S00392 | | 9 | C | | * | | | TB0118G | 7 | 2 | | 050-099 |
| 546 | 22 | | PA | 3-0 | 25-53-23 | S00392 | | 6 | C | | | | | L00158 | =P | \$ | | 050-099 |
| 547 | 22 | | PA | 1-0 | 25-53-23 | S00392 | | 7 | C | | | | | S00392 | 10 | C | * | 050-099 |
| 548 | 22 | | PA | 6-0 | 25-53-23 | S00392 | | 8 | C | | * | | | TB0118D | C038 | 2 | | 050-099 |
| 549 | 22 | | PA | 1-0 | 25-53-23 | S00392 | | 9 | C | | * | | | S00392 | 11 | C | | 050-099 |
| 550 | 22 | | PA | 5-0 | 25-53-23 | D02544 | | 1 | | | | | | TB0118G | 1 | 2 | | 050-099 |
| 550 | 22 | | PA | 4-0 | 25-53-23 | D02544 | | 1 | | | | | | TB0118G | 1 | 2 | | 150-199, 275-299 |
| 551 | 22 | | PA | 5-0 | 25-53-23 | D02544 | | 13 | | | | | | TB0118G | 3 | 2 | | 050-099 |
| 551 | 22 | | PA | 4-0 | 25-53-23 | D02544 | | 13 | | | | | | TB0118Z | 3 | BJ | | 150-199, 275-299 |
| 552 | 22 | | PA | 5-0 | 25-53-23 | D02544 | | 5 | | | | | | TB0118G | 2 | 2 | | 050-099 |
| 552 | 22 | | PA | 4-0 | 25-53-23 | D02544 | | 5 | | | | | | TB0118G | 2 | 2 | | 150-199, 275-299 |
| 553 | 22 | | PA | 5-0 | 25-53-23 | D02544 | | 3 | | | | | | TB0118G | 4 | 2 | | 050-099 |
| 553 | 22 | | PA | 4-0 | 25-53-23 | D02544 | | 3 | | | | | | TB0118Z | 4 | BJ | | 150-199, 275-299 |
| 554 | 22 | | PA | 5-0 | 25-53-23 | D02544 | | 11 | | | | | | TB0118H | 10 | 2 | | 050-099 |
| 555 | 22 | | PA | 5-0 | 25-53-23 | D02544 | | 9 | | | | | | TB0118G | 7 | 2 | | 050-099 |
| 555 | 22 | | PA | 4-0 | 25-53-23 | D02544 | | 9 | | | | | | TB0118Z | 10 | BJ | | 150-199, 275-299 |
| 556 | 22 | | PA | 5-0 | 25-53-25 | D02544 | | 14 | | | | | | TB0118G | 5 | 2 | | 050-099 |
| 556 | 22 | | PA | 1-0 | 25-53-25 | D02544 | | 14 | | | | | | D02558 | X1 | | | 150-199, 275-299 |
| 557 | 22 | | PA | 5-0 | 25-53-25 | D02544 | | 8 | | | | | | TB0118G | 6 | 2 | | 050-099 |
| 557 | 22 | | PA | 1-0 | 25-53-25 | D02544 | | 8 | | | | | | D02560 | X1 | | | 150-199, 275-299 |
| 558 | 22 | | PA | 5-0 | 25-53-23 | D02544 | | 10 | | | | | | TB0118H | 12 | 2 | | 050-099 |
| 558 | 22 | | PA | 4-0 | 25-53-23 | D02544 | | 10 | | | | | | TB0118Z | 12 | BJ | | 150-199, 275-299 |
| 559 | 22 | | PA | 5-0 | 25-53-23 | D02544 | | 12 | | | | | | TB0118H | 39 | 2 | | 050-099 |
| 559 | 22 | | PA | 5-0 | 25-53-23 | D02544 | | 12 | | | | | | TB0118Z | 39 | BJ | | 150-199, 275-299 |
| 566 | 22 | | PA | 6-0 | 25-53-23 | L00158 | | =G | \$ | | * | | | TB0122H | 5 | 2 | | 050-099 |
| 567 | 22 | | PA | 3-0 | 25-53-23 | L00158 | | =G | \$ | | * | | | L00157 | =G | \$ | * | 050-099 |
| 568 | 22 | | PA | 3-0 | 25-53-23 | L00159 | | =G | \$ | | | | | L00157 | =G | \$ | * | 050-099 |
| 571 | 22 | | PA | 3-0 | 25-53-23 | D02568 | | 2 | | | | | | TB0118H | 50 | 2 | | 050-099 |
| 572 | 22 | | PA | 2-0 | 25-53-23 | D02568 | | 5 | | | | | | TB0118G | 7 | 2 | | 050-099 |
| 573 | 22 | | PA | 3-0 | 25-53-25 | D02568 | | 3 | | | | | | TB0118H | 39 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 73

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | | |
| 573 | 22 | | PA | 1-0 | 25-53-24 | D11208 | | 6 | | | | | TB0118Z | 9 | BJ | | 150-199, 275-299 |
| 574 | 22 | | PA | 2-0 | 25-53-25 | D02568 | | 7 | | | | | TB0118G | 5 | 2 | | 050-099 |
| 574 | 22 | | PA | 2-0 | 25-53-24 | D11208 | | 3 | | | | | TB0118Z | 40 | BJ | | 150-199, 275-299 |
| 575 | 22 | | PA | 7-0 | 25-53-25 | D02558 | | X1 | | | | | S00395 | 2 | C | | 050-099 |
| 576 | 22 | | PA | 2-0 | 25-53-25 | D02558 | | X2 | | | | | TB0120H | 5 | 2 | | 050-099 |
| 576 | 22 | | PA | 3-0 | 25-53-25 | D02558 | | X2 | | | | | TB0118Z | 41 | BJ | | 150-199, 275-299 |
| 577 | 22 | | PA | 6-0 | 25-53-25 | TB0118G | | 5 | 2 | | | | S00395 | 1 | C | | 050-099 |
| 577 | 22 | | PA | 5-0 | 25-53-24 | D05250J | | 18 | | | | | TB0118G | 7 | 2 | | 150-199, 275-299 |
| 578 | 22 | | PA | 2-0 | 25-53-26 | D02554 | | X2 | | | | | TB0120H | 5 | 2 | | 050-099 |
| 578 | 22 | | PA | 3-0 | 25-53-26 | D02554 | | X2 | | | | | TB0118Z | 41 | BJ | | 150-199, 275-299 |
| 579 | 22 | | PA | 2-0 | 25-53-26 | D02556 | | X2 | | | | | TB0120H | 5 | 2 | | 050-099 |
| 579 | 22 | | PA | 3-0 | 25-53-26 | D02556 | | X2 | | | | | TB0118Z | 41 | BJ | | 150-199, 275-299 |
| 580 | 22 | | PA | 2-0 | 25-53-23 | TB0118H | | 39 | 2 | | | | TB0118H | 50 | 2 | | 050-099 |
| 580 | 22 | | PA | 1-0 | 25-53-23 | TB0118Z | | 41 | BJ | | | | TB0118Z | 42 | BJ | | 150-199, 275-299 |
| 581 | 22 | | PA | 2-0 | 25-53-23 | D02570 | | 2 | | | | | TB0118H | 50 | 2 | | 050-099 |
| 582 | 22 | | PA | 2-0 | 25-53-23 | D02570 | | 5 | | | | | TB0118H | 12 | 2 | | 050-099 |
| 583 | 22 | | PA | 3-0 | 25-53-25 | D02570 | | 3 | | | | | TB0118H | 39 | 2 | | 050-099 |
| 583 | 22 | | PA | 3-0 | 25-53-24 | D01786 | | X1 | | | | | D11208 | 5 | | | 150-199, 275-299 |
| 584 | 22 | | PA | 2-0 | 25-53-25 | D02570 | | 7 | | | | | TB0118G | 6 | 2 | | 050-099 |
| 584 | 22 | | PA | 3-0 | 25-53-24 | D01786 | | A1 | | | | | TB0118Z | 20 | BJ | | 150-199, 275-299 |
| 585 | 22 | | PA | 6-0 | 25-53-25 | D02560 | | X1 | | | | | S00394 | 2 | C | | 050-099 |
| 586 | 22 | | PA | 2-0 | 25-53-25 | D02560 | | X2 | | | | | TB0120H | 5 | 2 | | 050-099 |
| 586 | 22 | | PA | 3-0 | 25-53-25 | D02560 | | X2 | | | | | TB0118Z | 41 | BJ | | 150-199, 275-299 |
| 587 | 22 | | PA | 6-0 | 25-53-25 | TB0118G | | 6 | 2 | | | | S00394 | 1 | C | | 050-099 |
| 587 | 22 | | PA | 1-0 | 25-53-24 | D11208 | | 7 | | | | | TB0118G | 7 | 2 | | 150-199, 275-299 |
| 589 | 20 | | PA | 2-0 | 25-53-21 | K00278 | | 11 | C | * | | | TB0122H | 1 | 2 | | 050-099 |
| 589 | 20 | | PA | 4-0 | 25-53-21 | K00278 | | 11 | C | * | | | TB0118Z | 35 | BJ | | 150-199, 275-299 |
| 590 | 20 | | PA | 4-0 | 25-53-21 | K00278 | | 12 | C | | | | TB0120G | 15 | 2 | | ALL |
| 591 | 20 | | PA | 1-0 | 25-53-21 | K00278 | | 11 | C | * | | | K00278 | X1 | C | | ALL |
| 592 | 20 | | PA | 5-0 | 25-53-21 | D02566 | | 2 | | | | | K00278 | X2 | C | | 050-099 |
| 592 | 20 | | PA | 4-0 | 25-53-21 | D02566 | | 2 | | | | | K00278 | X2 | C | | 150-199, 275-299 |
| 593 | 20 | | PA | 5-0 | 25-53-21 | D02566 | | 7 | | | | | TB0122H | 1 | 2 | | 050-099 |
| 593 | 20 | | PA | 1-0 | 25-53-21 | D02566 | | 7 | | | | | TB0118Z | 35 | BJ | | 150-199, 275-299 |
| 594 | 20 | | PA | 5-0 | 33-37-21 | D02628 | | X1 | | | | | TB0122H | 1 | 2 | | 050-099 |
| 594 | 20 | | PA | 1-0 | 33-37-21 | D02628 | | X1 | | | | | TB0118Z | 35 | BJ | | 150-199, 275-299 |
| 595 | 20 | | PA | 1-0 | 33-37-21 | D02566 | | 6 | | | | | D02628 | X2 | | | ALL |
| 596 | 20 | | PA | 2-0 | 33-37-21 | TB0118H | | 39 | 2 | | | | D02566 | 1 | | | 050-099 |
| 596 | 20 | | PA | 2-0 | 33-37-21 | TB0118Z | | 39 | BJ | | | | D02566 | 1 | | | 150-199, 275-299 |
| 597 | 22 | | PA | 2-0 | 25-53-27 | D02562 | | X2 | | | | | TB0120H | 5 | 2 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W1060
Page 74
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | | |
| 597 | 20 | | PA | 4-0 | 25-53-21 | D02566 | | | 3 | | | | TB0122D | A001 | 2 | | 150-199, 275-299 |
| 598 | 22 | | PA | 2-0 | 25-53-27 | D02564 | | | X2 | | | | TB0120H | 5 | 2 | | 050-099 |
| 598 | 22 | | PA | 4-0 | 25-53-27 | D02564 | | | X2 | | | | TB0120H | 5 | 2 | | 150-199 |
| 599 | 20 | | PA | 5-0 | 25-53-21 | D02566 | | | 3 | | | | TB0122D | A | 2 | | 050-099 |
| 600 | 22 | | PA | 5-0 | 25-53-24 | D02548 | | | 6 | | | | TB0118H | 14 | 2 | | 050-099 |
| 600 | 22 | | PA | 3-0 | 25-53-24 | D02548 | | | 6 | | | | TB0118Z | 14 | BJ | | 150-199, 275-299 |
| 601 | 22 | | PA | 5-0 | 25-53-24 | D02548 | | | 1 | | | | D05258J | 1 | | | 050-099 |
| 601 | 22 | | PA | 3-0 | 25-53-24 | D02548 | | | 1 | | | | D05258J | 1 | | | 150-199, 275-299 |
| 602 | 22 | | PA | 5-0 | 25-53-24 | D02548 | | | 2 | | | | TB0118G | 22 | 2 | | 050-099 |
| 602 | 22 | | PA | 3-0 | 25-53-24 | D02548 | | | 2 | | | | TB0118G | 22 | 2 | | 150-199, 275-299 |
| 603 | 22 | | PA | 5-0 | 25-53-24 | D02548 | | | 5 | | | | D05258J | 2 | | | 050-099 |
| 603 | 22 | | PA | 3-0 | 25-53-24 | D02548 | | | 5 | | | | D05258J | 2 | | | 150-199, 275-299 |
| 608 | 22 | | PA | 5-0 | 25-53-23 | D02548 | | | 7 | | | | TB0118G | 3 | 2 | | 050-099 |
| 608 | 22 | | PA | 3-0 | 25-53-23 | D02548 | | | 7 | | | | TB0118Z | 3 | BJ | | 150-199, 275-299 |
| 609 | 22 | | PA | 4-0 | 25-53-23 | D02548 | | | 3 | | | | TB0118D | A037 | 2 | | 050-099 |
| 609 | 22 | | PA | 4-0 | 25-53-23 | D02548 | | | 3 | | | | TB0122D | A003 | 2 | | 150-199, 275-299 |
| 610 | 22 | | PA | 5-0 | 25-53-24 | D02546 | | | 6 | | | | TB0118H | 14 | 2 | | 050-099 |
| 610 | 22 | | PA | 3-0 | 25-53-24 | D02546 | | | 6 | | | | TB0118Z | 14 | BJ | | 150-199, 275-299 |
| 611 | 22 | | PA | 5-0 | 25-53-24 | D02546 | | | 1 | | | | D05258J | 4 | | | 050-099 |
| 611 | 22 | | PA | 3-0 | 25-53-24 | D02546 | | | 1 | | | | D05258J | 4 | | | 150-199, 275-299 |
| 612 | 22 | | PA | 5-0 | 25-53-24 | D02546 | | | 2 | | | | TB0118G | 22 | 2 | | 050-099 |
| 612 | 22 | | PA | 3-0 | 25-53-24 | D02546 | | | 2 | | | | TB0118G | 22 | 2 | | 150-199, 275-299 |
| 613 | 22 | | PA | 5-0 | 25-53-24 | D02546 | | | 5 | | | | D05258J | 5 | | | 050-099 |
| 613 | 22 | | PA | 3-0 | 25-53-24 | D02546 | | | 5 | | | | D05258J | 5 | | | 150-199, 275-299 |
| 618 | 22 | | PA | 5-0 | 25-53-23 | D02546 | | | 7 | | | | TB0118G | 4 | 2 | | 050-099 |
| 618 | 22 | | PA | 3-0 | 25-53-23 | D02546 | | | 7 | | | | TB0118Z | 4 | BJ | | 150-199, 275-299 |
| 619 | 22 | | PA | 5-0 | 25-53-23 | D02546 | | | 3 | | | | TB0122D | A | 2 | | 050-099 |
| 619 | 22 | | PA | 4-0 | 25-53-23 | D02546 | | | 3 | | | | TB0122D | A002 | 2 | | 150-199, 275-299 |
| 620 | 22 | | PA | 5-0 | 25-53-24 | D02552 | | | 6 | | | | TB0118H | 14 | 2 | | 050-099 |
| 620 | 22 | | PA | 3-0 | 25-53-24 | D02552 | | | 6 | | | | TB0118Z | 14 | BJ | | 150-199, 275-299 |
| 621 | 22 | | PA | 5-0 | 25-53-24 | D02552 | | | 1 | | | | D05258J | 7 | | | 050-099 |
| 621 | 22 | | PA | 3-0 | 25-53-24 | D02552 | | | 1 | | | | D05258J | 7 | | | 150-199, 275-299 |
| 622 | 22 | | PA | 5-0 | 25-53-24 | D02552 | | | 2 | | | | TB0118G | 24 | 2 | | 050-099 |
| 622 | 22 | | PA | 3-0 | 25-53-24 | D02552 | | | 2 | | | | TB0118G | 24 | 2 | | 150-199, 275-299 |
| 623 | 22 | | PA | 5-0 | 25-53-24 | D02552 | | | 5 | | | | D05258J | 8 | | | 050-099 |
| 623 | 22 | | PA | 3-0 | 25-53-24 | D02552 | | | 5 | | | | D05258J | 8 | | | 150-199, 275-299 |
| 628 | 22 | | PA | 5-0 | 25-53-23 | D02552 | | | 7 | | | | TB0118G | 3 | 2 | | 050-099 |
| 628 | 22 | | PA | 3-0 | 25-53-23 | D02552 | | | 7 | | | | TB0118Z | 3 | BJ | | 150-199, 275-299 |
| 629 | 22 | | PA | 4-0 | 25-53-23 | D02552 | | | 3 | | | | TB0118D | A038 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 75

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | |
| 629 | 22 | | PA | 4-0 | 25-53-23 | D02552 | | 3 | | TB0122D | A005 | 2 | | 150-199, 275-299 | |
| 630 | 22 | | PA | 5-0 | 25-53-24 | D02550 | | 6 | | TB0118H | 14 | 2 | | 050-099 | |
| 630 | 22 | | PA | 3-0 | 25-53-24 | D02550 | | 6 | | TB0118Z | 14 | BJ | | 150-199, 275-299 | |
| 631 | 22 | | PA | 5-0 | 25-53-24 | D02550 | | 1 | | D05258J | 11 | | | 050-099 | |
| 631 | 22 | | PA | 3-0 | 25-53-24 | D02550 | | 1 | | D05258J | 11 | | | 150-199, 275-299 | |
| 632 | 22 | | PA | 5-0 | 25-53-24 | D02550 | | 2 | | TB0118G | 24 | 2 | | 050-099 | |
| 632 | 22 | | PA | 3-0 | 25-53-24 | D02550 | | 2 | | TB0118G | 24 | 2 | | 150-199, 275-299 | |
| 633 | 22 | | PA | 5-0 | 25-53-24 | D02550 | | 5 | | D05258J | 12 | | | 050-099 | |
| 633 | 22 | | PA | 3-0 | 25-53-24 | D02550 | | 5 | | D05258J | 12 | | | 150-199, 275-299 | |
| 638 | 22 | | PA | 5-0 | 25-53-23 | D02550 | | 7 | | TB0118G | 4 | 2 | | 050-099 | |
| 638 | 22 | | PA | 3-0 | 25-53-23 | D02550 | | 7 | | TB0118Z | 4 | BJ | | 150-199, 275-299 | |
| 639 | 22 | | PA | 5-0 | 25-53-23 | D02550 | | 3 | | TB0122D | A | 2 | | 050-099 | |
| 639 | 22 | | PA | 4-0 | 25-53-23 | D02550 | | 3 | | TB0122D | A004 | 2 | | 150-199, 275-299 | |
| 640 | 22 | | PA | 4-0 | 25-53-24 | D02532 | | 6 | | TB0118G | 25 | 2 | | 050-099 | |
| 640 | 22 | | PA | 3-0 | 25-53-24 | D02532 | | 6 | | TB0118G | 25 | 2 | | 150-199, 275-299 | |
| 641 | 22 | | PA | 5-0 | 25-53-24 | D02532 | | 1 | | D05258J | 14 | | | 050-099 | |
| 641 | 22 | | PA | 3-0 | 25-53-24 | D02532 | | 1 | | D05258J | 14 | | | 150-199, 275-299 | |
| 642 | 22 | | PA | 4-0 | 25-53-24 | D02532 | | 2 | | TB0118G | 26 | 2 | | 050-099 | |
| 642 | 22 | | PA | 3-0 | 25-53-24 | D02532 | | 2 | | TB0118Z | 19 | BJ | | 150-199, 275-299 | |
| 643 | 22 | | PA | 5-0 | 25-53-24 | D02532 | | 5 | | D05258J | 15 | | | 050-099 | |
| 643 | 22 | | PA | 3-0 | 25-53-24 | D02532 | | 5 | | D05258J | 15 | | | 150-199, 275-299 | |
| 648 | 22 | | PA | 5-0 | 25-53-23 | D02532 | | 7 | | TB0118G | 3 | 2 | | 050-099 | |
| 648 | 22 | | PA | 3-0 | 25-53-23 | D02532 | | 7 | | TB0118Z | 3 | BJ | | 150-199, 275-299 | |
| 649 | 22 | | PA | 5-0 | 25-53-23 | D02532 | | 3 | | TB0118H | 8 | 2 | | 050-099 | |
| 649 | 22 | | PA | 4-0 | 25-53-23 | D02532 | | 3 | | TB0122D | A007 | 2 | | 150-199, 275-299 | |
| 650 | 22 | | PA | 4-0 | 25-53-24 | D02530 | | 6 | | TB0118G | 25 | 2 | | 050-099 | |
| 650 | 22 | | PA | 3-0 | 25-53-24 | D02530 | | 6 | | TB0118G | 25 | 2 | | 150-199, 275-299 | |
| 651 | 22 | | PA | 5-0 | 25-53-24 | D02530 | | 1 | | D05258J | 17 | | | 050-099 | |
| 651 | 22 | | PA | 3-0 | 25-53-24 | D02530 | | 1 | | D05258J | 17 | | | 150-199, 275-299 | |
| 652 | 22 | | PA | 4-0 | 25-53-24 | D02530 | | 2 | | TB0118G | 26 | 2 | | 050-099 | |
| 652 | 22 | | PA | 3-0 | 25-53-24 | D02530 | | 2 | | TB0118Z | 19 | BJ | | 150-199, 275-299 | |
| 653 | 22 | | PA | 5-0 | 25-53-24 | D02530 | | 5 | | D05258J | 18 | | | 050-099 | |
| 653 | 22 | | PA | 3-0 | 25-53-24 | D02530 | | 5 | | D05258J | 18 | | | 150-199, 275-299 | |
| 658 | 22 | | PA | 5-0 | 25-53-23 | D02530 | | 7 | | TB0118G | 4 | 2 | | 050-099 | |
| 658 | 22 | | PA | 3-0 | 25-53-23 | D02530 | | 7 | | TB0118Z | 4 | BJ | | 150-199, 275-299 | |
| 659 | 22 | | PA | 5-0 | 25-53-23 | D02530 | | 3 | | TB0118H | 8 | 2 | | 050-099 | |
| 659 | 22 | | PA | 4-0 | 25-53-23 | D02530 | | 3 | | TB0122D | A006 | 2 | | 150-199, 275-299 | |
| 660 | 22 | | PA | 4-0 | 25-53-24 | D02536 | | A2 | | TB0118G | 27 | 2 | | 050-099 | |
| 660 | 22 | | PA | 3-0 | 25-53-24 | D11200 | | 6 | | TB0118G | 27 | 2 | | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 76

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | | |
| 661 | 22 | | PA | 5-0 | 25-53-24 | D02536 | | A1 | | | | | D05258J | 21 | | | 050-099 |
| 661 | 22 | | PA | 4-0 | 25-53-24 | D11200 | | 1 | | | | | D05258J | 21 | | | 150-199, 275-299 |
| 662 | 22 | | PA | 4-0 | 25-53-24 | D02536 | | B2 | | | | | TB0118G | 28 | 2 | | 050-099 |
| 662 | 22 | | PA | 3-0 | 25-53-24 | D11200 | | 2 | | | | | TB0118G | 28 | 2 | | 150-199, 275-299 |
| 663 | 22 | | PA | 5-0 | 25-53-24 | D02536 | | B1 | | | | | D05258J | 22 | | | 050-099 |
| 663 | 22 | | PA | 4-0 | 25-53-24 | D11200 | | 5 | | | | | D05258J | 22 | | | 150-199, 275-299 |
| 664 | 22 | | PA | 4-0 | 25-53-24 | D02556 | | D2 | | | | | TB0118H | 30 | 2 | | 050-099 |
| 664 | 22 | | PA | 3-0 | 25-53-24 | D02556 | | D2 | | | | | TB0118G | 54 | 2 | | 150-199, 275-299 |
| 665 | 22 | | PA | 5-0 | 25-53-24 | TB0118G | | 33 | 2 | | | | D05258J | 23 | | | 050-099 |
| 665 | 22 | | PA | 4-0 | 25-53-24 | TB0118G | | 30 | 2 | | | | D05258J | 23 | | | 150-199, 275-299 |
| 668 | 22 | | PA | 5-0 | 25-53-23 | D02536 | | X1 | | | | | TB0118G | 1 | 2 | | 050-099 |
| 668 | 22 | | PA | 4-0 | 25-53-23 | D11200 | | 7 | | | | | TB0118G | 1 | 2 | | 150-199, 275-299 |
| 669 | 22 | | PA | 5-0 | 25-53-23 | D02536 | | X2 | | | | | TB0118H | 10 | 2 | | 050-099 |
| 669 | 22 | | PA | 3-0 | 25-53-23 | D11200 | | 3 | | | | | TB0118Z | 42 | BJ | | 150-199, 275-299 |
| 670 | 22 | | PA | 4-0 | 25-53-24 | D02534 | | A2 | | | | | TB0118G | 27 | 2 | | 050-099 |
| 670 | 22 | | PA | 3-0 | 25-53-24 | D11202 | | 6 | | | | | TB0118G | 27 | 2 | | 150-199, 275-299 |
| 671 | 22 | | PA | 5-0 | 25-53-24 | D02534 | | A1 | | | | | D05258J | 24 | | | 050-099 |
| 671 | 22 | | PA | 4-0 | 25-53-24 | D11202 | | 1 | | | | | D05258J | 24 | | | 150-199, 275-299 |
| 672 | 22 | | PA | 4-0 | 25-53-24 | D02534 | | B2 | | | | | TB0118G | 28 | 2 | | 050-099 |
| 672 | 22 | | PA | 3-0 | 25-53-24 | D11202 | | 2 | | | | | TB0118G | 28 | 2 | | 150-199, 275-299 |
| 673 | 22 | | PA | 5-0 | 25-53-24 | D02534 | | B1 | | | | | D05258J | 25 | | | 050-099 |
| 673 | 22 | | PA | 4-0 | 25-53-24 | D11202 | | 5 | | | | | D05258J | 25 | | | 150-199, 275-299 |
| 675 | 22 | | PA | 5-0 | 25-53-24 | TB0118G | | 33 | 2 | | | | D05258J | 26 | | | 050-099 |
| 675 | 22 | | PA | 4-0 | 25-53-24 | TB0118G | | 30 | 2 | | | | D05258J | 26 | | | 150-199, 275-299 |
| 676 | 22 | | PA | 4-0 | 25-53-24 | D02534 | | C2 | | | | | TB0118H | 43 | 2 | | 050-099 |
| 677 | 22 | | PA | 1-0 | 25-53-24 | D02534 | | C3 | | | | | D02536 | C3 | | | 050-099 |
| 678 | 22 | | PA | 5-0 | 25-53-23 | D02534 | | X1 | | | | | TB0118G | 2 | 2 | | 050-099 |
| 678 | 22 | | PA | 4-0 | 25-53-23 | D11202 | | 7 | | | | | TB0118G | 2 | 2 | | 150-199, 275-299 |
| 679 | 22 | | PA | 5-0 | 25-53-23 | D02534 | | X2 | | | | | TB0118H | 10 | 2 | | 050-099 |
| 679 | 22 | | PA | 3-0 | 25-53-23 | D11202 | | 3 | | | | | TB0118Z | 42 | BJ | | 150-199, 275-299 |
| 680 | 22 | | PA | 4-0 | 25-53-24 | D02538 | | A2 | | | | | TB0118H | 16 | 2 | | 050-099 |
| 680 | 22 | | PA | 4-0 | 25-53-24 | D11198 | | A2 | | | | | TB0118Z | 9 | BJ | | 150-199, 275-299 |
| 681 | 22 | | PA | 4-0 | 25-53-24 | D02538 | | A1 | | | | | TB0118H | 30 | 2 | | 050-099 |
| 681 | 22 | | PA | 3-0 | 25-53-24 | D11198 | | A1 | | | | | TB0118G | 54 | 2 | | 150-199, 275-299 |
| 682 | 22 | | PA | 4-0 | 25-53-24 | D02538 | | B2 | | | | | TB0118H | 20 | 2 | | 050-099 |
| 682 | 22 | | PA | 4-0 | 25-53-24 | D11198 | | B2 | | | | | TB0118Z | 8 | BJ | | 150-199, 275-299 |
| 683 | 22 | | PA | 4-0 | 25-53-24 | D02538 | | B1 | | | | | D05258J | 10 | | | 050-099 |
| 683 | 22 | | PA | 4-0 | 25-53-24 | D11198 | | B1 | | | | | D05258J | 10 | | | 150-199, 275-299 |
| 684 | 22 | | PA | 3-0 | 25-53-24 | TB0118Y | | A054 | BJ | | | | D02556 | C2 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 77

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | |
| 684 | 22 | | PA | 3-0 | 25-53-24 | TB0118Z | 51 | BJ | | D02556 | C2 | | | 150-199, 275-299 | | |
| 685 | 22 | | PA | 4-0 | 25-53-24 | D02538 | C3 | | | TB0118G | 33 | 2 | | 050-099 | | |
| 685 | 22 | | PA | 4-0 | 25-53-24 | D11198 | C3 | | | TB0118G | 30 | 2 | | 150-199, 275-299 | | |
| 687 | 22 | | PA | 6-0 | 25-53-24 | D02536 | C2 | | | D05258J | 40 | | | 050-099 | | |
| 688 | 22 | | PA | 3-0 | 25-53-23 | D02538 | X1 | | | TB0118Y | C052 | BJ | | 050-099 | | |
| 689 | 22 | | PA | 3-0 | 25-53-23 | D02538 | X2 | | | TB0118H | 50 | 2 | | 050-099 | | |
| 689 | 22 | | PA | 3-0 | 25-53-23 | D11198 | X2 | | | TB0118Z | 42 | BJ | | 150-199, 275-299 | | |
| 690 | 22 | | PA | 4-0 | 25-53-24 | D02542 | 6 | | | TB0118H | 20 | 2 | | 050-099 | | |
| 690 | 22 | | PA | 4-0 | 25-53-24 | D11204 | 6 | | | TB0118Z | 20 | BJ | | 150-199, 275-299 | | |
| 691 | 22 | | PA | 5-0 | 25-53-24 | D02542 | 1 | | | D05258J | 27 | | | 050-099 | | |
| 691 | 22 | | PA | 4-0 | 25-53-24 | D11204 | 1 | | | D05258J | 27 | | | 150-199, 275-299 | | |
| 692 | 22 | | PA | 4-0 | 25-53-24 | D02542 | 2 | | | TB0118G | 32 | 2 | | 050-099 | | |
| 692 | 22 | | PA | 4-0 | 25-53-24 | D11204 | 2 | | | TB0118G | 32 | 2 | | 150-199, 275-299 | | |
| 693 | 22 | | PA | 5-0 | 25-53-24 | D02542 | 5 | | | D05258J | 28 | | | 050-099 | | |
| 693 | 22 | | PA | 4-0 | 25-53-24 | D11204 | 5 | | | D05258J | 28 | | | 150-199, 275-299 | | |
| 697 | 22 | | PA | 1-0 | 25-53-23 | TB0118G | 7 | 2 | | TB0118H | 8 | 2 | | 050-099 | | |
| 698 | 22 | | PA | 2-0 | 25-53-23 | D02542 | 7 | | | D02544 | 2 | | | 050-099 | | |
| 698 | 22 | | PA | 1-0 | 25-53-23 | D11204 | 7 | | | D02544 | 2 | | | 150-199, 275-299 | | |
| 699 | 22 | | PA | 4-0 | 25-53-23 | D02542 | 3 | | | TB0118H | 12 | 2 | | 050-099 | | |
| 699 | 22 | | PA | 3-0 | 25-53-23 | D11194 | 3 | | | TB0118Z | 11 | BJ | | 150-199, 275-299 | | |
| 700 | 22 | | PA | 4-0 | 25-53-24 | D02540 | 6 | | | TB0118H | 20 | 2 | | 050-099 | | |
| 700 | 22 | | PA | 3-0 | 25-53-24 | D11206 | 6 | | | TB0118Z | 20 | BJ | | 150-199, 275-299 | | |
| 701 | 22 | | PA | 4-0 | 25-53-24 | D02540 | 1 | | | D05258J | 31 | | | 050-099 | | |
| 701 | 22 | | PA | 4-0 | 25-53-24 | D11206 | 1 | | | D05258J | 31 | | | 150-199, 275-299 | | |
| 702 | 22 | | PA | 3-0 | 25-53-24 | D02540 | 2 | | | TB0118G | 32 | 2 | | 050-099 | | |
| 702 | 22 | | PA | 3-0 | 25-53-24 | D11206 | 2 | | | TB0118G | 32 | 2 | | 150-199, 275-299 | | |
| 703 | 22 | | PA | 4-0 | 25-53-24 | D02540 | 5 | | | D05258J | 32 | | | 050-099 | | |
| 703 | 22 | | PA | 4-0 | 25-53-24 | D11206 | 5 | | | D05258J | 32 | | | 150-199, 275-299 | | |
| 707 | 22 | | PA | 3-0 | 25-53-26 | D11852 | 2 | | | TB0118Y | A055 | BJ | | 050-099 | | |
| 707 | 22 | | PA | 4-0 | 25-53-26 | D11852 | 2 | | | TB0118Z | 15 | BJ | | 150-199, 275-299 | | |
| 708 | 22 | | PA | 2-0 | 25-53-23 | D02540 | 7 | | | D02544 | 4 | | | 050-099 | | |
| 708 | 22 | | PA | 1-0 | 25-53-23 | D11206 | 7 | | | D02544 | 4 | | | 150-199, 275-299 | | |
| 709 | 22 | | PA | 4-0 | 25-53-23 | D02540 | 3 | | | TB0118H | 12 | 2 | | 050-099 | | |
| 709 | 22 | | PA | 3-0 | 25-53-23 | D11196 | 3 | | | TB0118Z | 11 | BJ | | 150-199, 275-299 | | |
| 727 | 22 | | PA | 5-0 | 25-53-26 | TB0118G | 23 | 2 | | TB0122D | A011 | 2 | | 150-199, 275-299 | | |
| 728 | 22 | | PA | 6-0 | 25-53-26 | D11852 | 7 | | | TB0308Y | C002 | BJ | | 050-099 | | |
| 728 | 22 | | PA | 4-0 | 25-53-26 | D11852 | 7 | | | TB0118G | 23 | 2 | | 150-199, 275-299 | | |
| 729 | 22 | | PA | 4-0 | 25-53-26 | D11852 | 3 | | | TB0118Z | 41 | BJ | | 050-099 | | |
| 729 | 22 | | PA | 4-0 | 25-53-26 | D11852 | 3 | | | TB0118Z | 36 | BJ | | 150-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11
Section W1060
Page 78
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | |
| 730 | 22 | | PA | 2-0 | 25-53-24 | TB0118H | 14 | | 2 | | TB0118H | 16 | | 2 | 050-099 | |
| 730 | 22 | | PA | 3-0 | 25-53-24 | D01784 | | B1 | | | TB0118Z | 14 | | BJ | 150-199, 275-299 | |
| 731 | 22 | | PA | 2-0 | 25-53-24 | TB0118H | 18 | | 2 | | TB0118H | 20 | | 2 | 050-099 | |
| 736 | 22 | | PA | 2-0 | 25-53-24 | D02572 | | | 2 | | TB0118H | 18 | | 2 | 050-099 | |
| 736 | 22 | | PA | 1-0 | 25-53-24 | D02572 | | | 2 | | TB0118Z | 18 | | BJ | 150-199, 275-299 | |
| 737 | 22 | | PA | 2-0 | 25-53-24 | D02572 | | | 5 | | TB0118G | 22 | | 2 | ALL | |
| 738 | 22 | | PA | 2-0 | 25-53-24 | D02572 | | | 7 | | TB0118G | 29 | | 2 | 050-099 | |
| 738 | 22 | | PA | 1-0 | 25-53-24 | D02572 | | | 7 | | TB0118Z | 19 | | BJ | 150-199, 275-299 | |
| 739 | 22 | | PA | 3-0 | 25-53-23 | D02572 | | | 3 | | TB0118D | C037 | | 2 | 050-099 | |
| 739 | 22 | | PA | 1-0 | 25-53-23 | D02572 | | | 3 | | TB0118Z | 10 | | BJ | 150-199, 275-299 | |
| 741 | 22 | | PA | 2-0 | 25-53-24 | TB0118G | 29 | | 2 | | TB0118G | 26 | | 2 | 050-099 | |
| 746 | 22 | | PA | 2-0 | 25-53-24 | D02576 | | | 2 | | TB0118H | 18 | | 2 | 050-099 | |
| 746 | 22 | | PA | 1-0 | 25-53-24 | D02576 | | | 2 | | TB0118Z | 18 | | BJ | 150-199, 275-299 | |
| 747 | 22 | | PA | 2-0 | 25-53-24 | D02576 | | | 5 | | TB0118G | 24 | | 2 | ALL | |
| 748 | 22 | | PA | 2-0 | 25-53-24 | D02576 | | | 7 | | TB0118G | 29 | | 2 | 050-099 | |
| 748 | 22 | | PA | 2-0 | 25-53-24 | D02576 | | | 7 | | TB0118Z | 19 | | BJ | 150-199, 275-299 | |
| 749 | 22 | | PA | 3-0 | 25-53-23 | D02576 | | | 3 | | TB0118D | C038 | | 2 | 050-099 | |
| 749 | 22 | | PA | 1-0 | 25-53-23 | D02576 | | | 3 | | TB0118Z | 10 | | BJ | 150-199, 275-299 | |
| 750 | 22 | | PA | 2-0 | 25-53-24 | D02578 | | | 2 | | TB0118H | 14 | | 2 | 050-099 | |
| 750 | 22 | | PA | 1-0 | 25-53-24 | D02578 | | | 6 | | TB0118Z | 14 | | BJ | 150-199, 275-299 | |
| 751 | 22 | | PA | 3-0 | 25-53-24 | D02578 | | | 5 | | TB0118G | 25 | | 2 | 050-099 | |
| 751 | 22 | | PA | 2-0 | 25-53-24 | D02578 | | | 1 | | TB0118G | 25 | | 2 | 150-199, 275-299 | |
| 752 | 22 | | PA | 2-0 | 25-53-24 | D02578 | | | 7 | | TB0118H | 14 | | 2 | 050-099 | |
| 753 | 22 | | PA | 2-0 | 25-53-23 | D02578 | | | 3 | | TB0118H | 8 | | 2 | 050-099 | |
| 753 | 22 | | PA | 1-0 | 25-53-23 | D02578 | | | 3 | | TB0118Z | 10 | | BJ | 150-199, 275-299 | |
| 754 | 22 | | PA | 6-0 | 25-53-26 | D11660 | | | 10 | | TB0308Y | C002 | | BJ | 050-099 | |
| 754 | 22 | | PA | 5-0 | 25-53-26 | D11660 | | | 10 | | TB0118G | 23 | | 2 | 150-199, 275-299 | |
| 755 | 22 | | PA | 3-0 | 25-53-26 | D11662 | | | 2 | | TB0120D | C021 | | 2 | 050-099 | |
| 755 | 22 | | PA | 4-0 | 25-53-26 | D11662 | | | 2 | | TB0122D | C011 | | 2 | 150-199, 275-299 | |
| 756 | 22 | | PA | 2-0 | 25-53-24 | D02580 | | | 2 | | TB0118H | 18 | | 2 | 050-099 | |
| 756 | 22 | | PA | 1-0 | 25-53-24 | D02580 | | | 2 | | TB0118Z | 18 | | BJ | 150-199, 275-299 | |
| 757 | 22 | | PA | 2-0 | 25-53-24 | D02580 | | | 5 | | TB0118G | 26 | | 2 | 050-099 | |
| 757 | 22 | | PA | 1-0 | 25-53-24 | D02580 | | | 5 | | TB0118Z | 19 | | BJ | 150-199, 275-299 | |
| 758 | 22 | | PA | 2-0 | 25-53-24 | D02580 | | | 7 | | TB0118H | 18 | | 2 | 050-099 | |
| 758 | 22 | | PA | 1-0 | 25-53-24 | D02580 | | | 7 | | TB0118Z | 13 | | BJ | 150-199, 275-299 | |
| 759 | 22 | | PA | 2-0 | 25-53-23 | D02580 | | | 3 | | TB0118H | 8 | | 2 | 050-099 | |
| 759 | 22 | | PA | 1-0 | 25-53-23 | D02580 | | | 3 | | TB0118Z | 10 | | BJ | 150-199, 275-299 | |
| 760 | 22 | | PA | 2-0 | 25-53-24 | D02582 | | | 2 | | TB0118H | 16 | | 2 | 050-099 | |
| 760 | 22 | | PA | 1-0 | 25-53-24 | D11186 | | | 2 | | TB0118Z | 16 | | BJ | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 79

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | |
| 761 | 22 | | PA | 2-0 | 25-53-24 | D02582 | | 5 | | | TB0118G | 27 | 2 | | 050-099 |
| 761 | 22 | | PA | 2-0 | 25-53-24 | D11186 | | 5 | | | TB0118G | 27 | 2 | | 150-199, 275-299 |
| 762 | 22 | | PA | 2-0 | 25-53-24 | D02582 | | 7 | | | TB0118H | 16 | 2 | | 050-099 |
| 762 | 22 | | PA | 1-0 | 25-53-24 | D11186 | | 7 | | | TB0118Z | 16 | BJ | | 150-199, 275-299 |
| 763 | 22 | | PA | 2-0 | 25-53-23 | D02582 | | 3 | | | TB0118H | 10 | 2 | | 050-099 |
| 763 | 22 | | PA | 3-0 | 25-53-23 | D11182 | | 3 | | | TB0118Z | 11 | BJ | | 150-199, 275-299 |
| 766 | 22 | | PA | 2-0 | 25-53-24 | D02584 | | 2 | | | TB0118H | 20 | 2 | | 050-099 |
| 766 | 22 | | PA | 1-0 | 25-53-24 | D11184 | | 2 | | | TB0118Z | 20 | BJ | | 150-199, 275-299 |
| 767 | 22 | | PA | 2-0 | 25-53-24 | D02584 | | 5 | | | TB0118G | 28 | 2 | | 050-099 |
| 767 | 22 | | PA | 2-0 | 25-53-24 | D11184 | | 5 | | | TB0118G | 28 | 2 | | 150-199, 275-299 |
| 768 | 22 | | PA | 2-0 | 25-53-24 | D02584 | | 7 | | | TB0118H | 20 | 2 | | 050-099 |
| 768 | 22 | | PA | 1-0 | 25-53-24 | D11184 | | 7 | | | TB0118Z | 20 | BJ | | 150-199, 275-299 |
| 769 | 22 | | PA | 2-0 | 25-53-23 | D02584 | | 3 | | | TB0118H | 10 | 2 | | 050-099 |
| 769 | 22 | | PA | 1-0 | 25-53-23 | D02588 | | 3 | | | TB0118Z | 11 | BJ | | 150-199, 275-299 |
| 774 | 22 | | PA | 4-0 | 25-53-24 | D02556 | | C1 | | | TB0118H | 43 | 2 | | 050-099 |
| 774 | 22 | | PA | 3-0 | 25-53-24 | D02556 | | C1 | | | TB0118G | 43 | 2 | | 150-199, 275-299 |
| 775 | 22 | | PA | 4-0 | 25-53-24 | D05258J | | 20 | | | TB0118H | 30 | 2 | | 050-099 |
| 775 | 22 | | PA | 3-0 | 25-53-24 | D05258J | | 20 | | | TB0118G | 54 | 2 | | 150-199, 275-299 |
| 777 | 22 | | PA | 5-0 | 25-53-24 | D02556 | | D1 | | | D05258J | 30 | | | ALL |
| 786 | 22 | | PA | 2-0 | 25-53-24 | D02588 | | 2 | | | TB0118H | 16 | 2 | | 050-099 |
| 786 | 22 | | PA | 1-0 | 25-53-24 | D11188 | | 2 | | | TB0118Z | 16 | BJ | | 150-199, 275-299 |
| 787 | 22 | | PA | 2-0 | 25-53-24 | D02588 | | 5 | | | TB0118G | 32 | 2 | | 050-099 |
| 787 | 22 | | PA | 2-0 | 25-53-24 | D11188 | | 5 | | | TB0118G | 32 | 2 | | 150-199, 275-299 |
| 788 | 22 | | PA | 2-0 | 25-53-24 | D02588 | | 7 | | | TB0118H | 16 | 2 | | 050-099 |
| 788 | 22 | | PA | 1-0 | 25-53-24 | D11188 | | 7 | | | TB0118Z | 16 | BJ | | 150-199, 275-299 |
| 789 | 22 | | PA | 2-0 | 25-53-23 | D02588 | | 3 | | | TB0118H | 12 | 2 | | 050-099 |
| 792 | 22 | | PA | 1-0 | 25-53-24 | D11208 | | 2 | | | TB0118Z | 8 | BJ | | 150-199, 275-299 |
| 799 | 22 | | PA | 5-0 | 25-53-24 | D05250J | | 14 | | | TB0118Z | 9 | BJ | | 150-199, 275-299 |
| 800 | 22 | | PA | 3-0 | 25-53-26 | D11660 | | 14 | | | TB0120D | A021 | 2 | | 050-099 |
| 800 | 22 | | PA | 5-0 | 25-53-26 | D11660 | | 14 | | | TB0122D | A011 | 2 | | 150-199, 275-299 |
| 801 | 24 | | PK | 3-0 | 52-35-12 | D05888J | | 1 | | | S00413 | 12 | C | | ALL |
| 802 | 24 | | PK | 4-0 | 52-35-12 | D05888J | | 2 | | | TB0118G | 49 | 2 | | 050-099 |
| 802 | 24 | | PK | 3-0 | 52-35-12 | D05888J | | 2 | | | TB0118G | 49 | 2 | | 150-199, 275-299 |
| 803 | 24 | | PK | 4-0 | 52-35-12 | D05888J | | 3 | | | TB0118G | 48 | 2 | | 050-099 |
| 803 | 24 | | PK | 3-0 | 52-35-12 | D05888J | | 3 | | | TB0118G | 48 | 2 | | 150-199, 275-299 |
| 804 | 24 | | PK | 3-0 | 52-35-12 | D05888J | | 4 | | | TB0122G | 7 | 2 | | 050-099 |
| 804 | 24 | | PK | 3-0 | 52-35-12 | D05888J | | 4 | | | TB0118G | 50 | 2 | | 150-199, 275-299 |
| 805 | 24 | | PK | 3-0 | 52-35-12 | D05888J | | 5 | | | TB0122G | 8 | 2 | | 050-099 |
| 805 | 24 | | PK | 4-0 | 52-35-12 | D05888J | | 5 | | | TB0118G | 44 | 2 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 80

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | | | |
| 806 | 22 | | PA | 5-0 | 25-53-26 | D11662 | | 4 | | | | | | TB0308Z | 13 | BJ | | 050-099 |
| 806 | 22 | | PA | 3-0 | 25-53-26 | D11662 | | 4 | | | | | | TB0118Z | 52 | BJ | | 150-199, 275-299 |
| 807 | 24 | | PK | 3-0 | 52-35-12 | D05888J | | 7 | | | | | | R00037 | A | 2 | | 050-099 |
| 807 | 24 | | PK | 2-0 | 52-35-12 | D05888J | | 7 | | | | | | TB0122D | A010 | 2 | | 150-199, 275-299 |
| 814 | 24 | | PK | 3-0 | 52-35-12 | S00414 | | 2 | C | | * | | | TB0122G | 7 | 2 | | 050-099 |
| 814 | 24 | | PK | 3-0 | 52-35-12 | S00414 | | 2 | C | | * | | | TB0118G | 50 | 2 | | 150-199, 275-299 |
| 815 | 24 | | PK | 2-0 | 52-35-12 | S00414 | | 2 | C | | * | | | S00414 | 5 | C | | 050-099 |
| 815 | 24 | | PK | 1-0 | 52-35-12 | S00414 | | 2 | C | | * | | | S00414 | 5 | C | | 150-199, 275-299 |
| 816 | 24 | | PK | 3-0 | 52-35-12 | S00414 | | 1 | C | | * | | | TB0122G | 8 | 2 | | 050-099 |
| 816 | 24 | | PK | 3-0 | 52-35-12 | S00414 | | 1 | C | | * | | | TB0118G | 44 | 2 | | 150-199, 275-299 |
| 817 | 24 | | PK | 2-0 | 52-35-12 | S00414 | | 1 | C | | * | | | S00414 | 6 | C | * | 050-099 |
| 817 | 24 | | PK | 1-0 | 52-35-12 | S00414 | | 1 | C | | * | | | S00414 | 6 | C | * | 150-199, 275-299 |
| 818 | 24 | | PK | 2-0 | 52-35-12 | S00413 | | 8 | C | | | | | S00414 | 6 | C | * | ALL |
| 819 | 24 | | PK | 4-0 | 52-35-12 | S00413 | | 9 | C | | | | | TB0118G | 48 | 2 | | 050-099 |
| 819 | 24 | | PK | 3-0 | 52-35-12 | S00413 | | 9 | C | | | | | TB0118G | 48 | 2 | | 150-199, 275-299 |
| 820 | 24 | | PK | 2-0 | 52-35-12 | S00413 | | 7 | C | | | | | S00413 | 11 | C | | 050-099 |
| 820 | 24 | | PK | 1-0 | 52-35-12 | S00413 | | 7 | C | | | | | S00413 | 11 | C | | 150-199, 275-299 |
| 821 | 24 | | PK | 4-0 | 52-35-12 | S00413 | | 10 | C | | | | | TB0118G | 49 | 2 | | ALL |
| 822 | 24 | | PK | 5-0 | 52-35-12 | D02510 | | X1 | | | | | | TB0122G | 8 | 2 | | 050-099 |
| 822 | 24 | | PK | 1-0 | 52-35-12 | D02510 | | X1 | | | | | | TB0118G | 44 | 2 | | 150-199, 275-299 |
| 823 | 24 | | PK | 2-0 | 52-35-12 | D02510 | | X2 | | | | | | TB0118H | 39 | 2 | | 050-099 |
| 823 | 24 | | PK | 2-0 | 52-35-12 | D02510 | | X2 | | | | | | TB0118Z | 39 | BJ | | 150-199, 275-299 |
| 824 | 24 | | PK | 2-0 | 52-35-12 | D02516 | | X1 | | | | | | TB0118G | 48 | 2 | | 050-099 |
| 824 | 24 | | PK | 1-0 | 52-35-12 | D02516 | | X1 | | | | | | TB0118G | 48 | 2 | | 150-199, 275-299 |
| 825 | 24 | | PK | 2-0 | 52-35-12 | D02518 | | X1 | | | | | | TB0118G | 49 | 2 | | 050-099 |
| 825 | 24 | | PK | 1-0 | 52-35-12 | D02518 | | X1 | | | | | | TB0118G | 49 | 2 | | 150-199, 275-299 |
| 826 | 22 | | PA | 5-0 | 25-53-26 | D11662 | | 1 | | | | | | TB0308Y | C001 | BJ | | 050-099 |
| 826 | 22 | | PA | 3-0 | 25-53-26 | D11662 | | 1 | | | | | | TB0118G | 55 | 2 | | 150-199, 275-299 |
| 827 | 22 | | PA | 4-0 | 25-53-26 | D11664 | | 1 | | | | | | TB0118H | 43 | 2 | | 050-099 |
| 827 | 22 | | PA | 3-0 | 25-53-26 | D11664 | | 1 | | | | | | TB0118G | 43 | 2 | | 150-199, 275-299 |
| 828 | 24 | | PK | 2-0 | 52-35-12 | D02512 | | X1 | | | | | | TB0118G | 48 | 2 | | ALL |
| 829 | 24 | | PK | 2-0 | 52-35-12 | D02514 | | X1 | | | | | | TB0118G | 49 | 2 | | ALL |
| 833 | 22 | | PA | 2-0 | 25-53-26 | D11662 | | 7 | | | | | | TB0118Y | C052 | BJ | | 050-099 |
| 833 | 22 | | PA | 4-0 | 25-53-26 | D11662 | | 7 | | | | | | TB0118Z | 34 | BJ | | 150-199, 275-299 |
| 834 | 22 | | PA | 2-0 | 25-53-26 | D11662 | | 3 | | | | | | TB0118Z | 41 | BJ | | 050-099 |
| 834 | 22 | | PA | 4-0 | 25-53-26 | D11662 | | 3 | | | | | | TB0118Z | 36 | BJ | | 150-199, 275-299 |
| 836 | 22 | | PA | 2-0 | 25-53-26 | D11662 | | 6 | | | | | | TB0118Y | A055 | BJ | | 050-099 |
| 836 | 22 | | PA | 4-0 | 25-53-26 | D11662 | | 6 | | | | | | TB0118Z | 15 | BJ | | 150-199, 275-299 |
| 837 | 22 | | PA | 3-0 | 25-53-26 | D11660 | | 12 | | | | | | TB0118Z | 41 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1060

Page 81

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | | | |
| 837 | 22 | | PA | 4-0 | 25-53-26 | D11660 | | 12 | | | | | TB0118Z | 36 | BJ | | 150-199, 275-299 |
| 838 | 22 | | PA | 3-0 | 25-53-26 | D11660 | | 6 | | | | | TB0118Y | A052 | BJ | | 050-099 |
| 838 | 22 | | PA | 4-0 | 25-53-26 | D11660 | | 6 | | | | | TB0118Z | 17 | BJ | | 150-199, 275-299 |
| 839 | 22 | | PA | 3-0 | 25-53-26 | D11660 | | 7 | | | | | TB0118Y | A053 | BJ | | 050-099 |
| 839 | 22 | | PA | 5-0 | 25-53-26 | D11660 | | 7 | | | | | TB0118Z | 8 | BJ | | 150-199, 275-299 |
| 840 | 22 | | PA | 3-0 | 25-53-26 | D11660 | | 11 | | | | | TB0118Y | C053 | BJ | | 050-099 |
| 840 | 22 | | PA | 5-0 | 25-53-26 | D11660 | | 11 | | | | | TB0118Z | 9 | BJ | | 150-199, 275-299 |
| 843 | 22 | | PA | 5-0 | 25-53-26 | D11668 | | 7 | | | | | TB0308Z | 13 | BJ | | 050-099 |
| 845 | 22 | | PA | 3-0 | 25-53-23 | D02544 | | 6 | | | | | TB0118Y | A052 | BJ | | 050-099 |
| 846 | 22 | | PA | 3-0 | 25-53-24 | D05250J | | 14 | | | | | TB0118Y | C053 | BJ | | 050-099 |
| 847 | 22 | | PA | 3-0 | 25-53-24 | D05250J | | 15 | | | | | TB0118Y | A053 | BJ | | 050-099 |
| 848 | 22 | | PA | 3-0 | 25-53-24 | D02538 | | C2 | | | | | TB0118Y | A054 | BJ | | 050-099 |
| 849 | 22 | | PA | 3-0 | 25-53-26 | D02538 | | D2 | | | | | TB0118Z | 41 | BJ | | 050-099 |
| 868 | 20 | | PA | 4-0 | 25-53-21 | TB0120G | | 15 | 2 | | | | C00075 | 2 | D | | 050-099 |
| 868 | 20 | | PA | 5-0 | 25-53-21 | TB0120G | | 15 | 2 | | | | C00075 | 2 | D | | 150-199, 275-299 |
| 869 | 20 | | PA | 5-0 | 25-53-21 | TB0120G | | 15 | 2 | | | | C00078 | 2 | D | | 050-099 |
| 869 | 20 | | PA | 6-0 | 25-53-21 | TB0120G | | 15 | 2 | | | | C00078 | 2 | D | | 150-199, 275-299 |
| 870 | 22 | | PA | 5-0 | 25-53-24 | TB0118G | | 23 | 2 | | | | C00078 | 1 | D | | 050-099 |
| 870 | 22 | | PA | 5-0 | 25-53-24 | TB0118G | | 31 | 2 | | | | C00078 | 1 | D | | 150-199, 275-299 |
| 871 | 22 | | PA | 4-0 | 25-53-24 | TB0118G | | 23 | 2 | | | | D01784 | A2 | | | 050-099 |
| 871 | 22 | | PA | 3-0 | 25-53-24 | TB0118G | | 31 | 2 | | | | D01784 | A2 | | | 150-199, 275-299 |
| 872 | 22 | | PA | 5-0 | 25-53-24 | TB0118H | | 14 | 2 | | | | D01784 | A1 | | | 050-099 |
| 872 | 22 | | PA | 4-0 | 25-53-24 | TB0118Z | | 16 | BJ | | | | D01784 | A1 | | | 150-199, 275-299 |
| 873 | 22 | | PA | 4-0 | 25-53-24 | TB0118H | | 50 | 2 | | | | D01784 | X2 | | | 050-099 |
| 873 | 22 | | PA | 3-0 | 25-53-24 | TB0118Z | | 41 | BJ | | | | D01784 | X2 | | | 150-199, 275-299 |
| 874 | 22 | | PA | 4-0 | 25-53-24 | TB0118G | | 23 | 2 | | | | D01786 | A2 | | | 050-099 |
| 874 | 22 | | PA | 3-0 | 25-53-24 | TB0118G | | 31 | 2 | | | | D01786 | A2 | | | 150-199, 275-299 |
| 875 | 22 | | PA | 4-0 | 25-53-24 | TB0118H | | 18 | 2 | | | | D01786 | A1 | | | 050-099 |
| 875 | 22 | | PA | 4-0 | 25-53-24 | TB0118Z | | 18 | BJ | | | | D01786 | B1 | | | 150-199, 275-299 |
| 876 | 22 | | PA | 4-0 | 25-53-24 | TB0118H | | 50 | 2 | | | | D01786 | X2 | | | 050-099 |
| 876 | 22 | | PA | 3-0 | 25-53-24 | TB0118Z | | 41 | BJ | | | | D01786 | X2 | | | 150-199, 275-299 |
| 877 | 22 | | PA | 3-0 | 25-53-21 | TB0122H | | 3 | 2 | | | | C00075 | 1 | D | | 050-099 |
| 883 | 22 | | PA | 5-0 | 25-53-25 | TB0122H | | 3 | 2 | | | | S00395 | 3 | C | | 050-099 |
| 884 | 22 | | PA | 5-0 | 25-53-25 | TB0122H | | 3 | 2 | | | | S00394 | 3 | C | | 050-099 |
| 887 | 22 | | PA | 5-0 | 25-53-21 | C00075 | | 1 | D | | | | TB0118Z | 33 | BJ | | 150-199, 275-299 |
| A-A | | | | 0-0 | 23-41-11 | D08555 | | | RED | | | | SM00001 | | S | | ALL |
| A-B | | | | 0-0 | 23-41-11 | D08555 | | | BLU | | | | SM00002 | | S | | ALL |
| A-C | | | | 0-0 | 23-41-11 | D08555 | | | BLK | | | | SM00003 | | S | | ALL |
| PA1 | | | | 0-0 | 99-99-99 | D02512 | | | G2 | | | | D02512 | G3 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1060
Page 82
Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|--------|-------|------|---------|--------|-------------|--|-----|
| | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | | |
| W1068 | 286T1068 | | | AFT CARGO LOADING ACCESSORY PANEL P39 (continued) | | | | | | | | | | | |
| PB1 | | | | | 0-0 | 99-99-99 | D02510 | | G2 | | D02510 | | G3 | | ALL |
| PC1 | | | | | 0-0 | 99-99-99 | D02514 | | G2 | | D02514 | | G3 | | ALL |
| PD1 | | | | | 0-0 | 99-99-99 | D02628 | | G2 | | D02628 | | G3 | | ALL |
| W1069 | 286T1069 | | | E2-3 SHELF,R ATC BOTTOM ANT COAX | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-53-13 | D00359B | | = C71 | | D04085P | | = C1 | | ALL |
| 01CX | | | | JB A | 5-0 | 34-53-13 | D00359B | | 71 | | D04085P | | = A1 | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1071 | 286T1071 | | | | E2-3 SHELF,R DME COAX | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-55-21 | D00361B | = C71 | | | D04105P | = C1 | | | ALL | |
| 01CX | | JB | A | 6-0 | 34-55-21 | D00361B | 71 | | | D04105P | = A1 | | | ALL | |
| W1073 | 286T1073 | | | | E2-5 SHELF,L VHF COAX | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-12-11 | D00439C | = C1 | | | D04009P | = C1 | | | ALL | |
| 01CX | | BR | A | 2-0 | 23-12-11 | D00439C | 1 | | | D04009P | = A1 | | | ALL | |
| W1075 | 286T1075 | | | | E2-5 SHELF,R VHF COAX | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-12-21 | D00443C | = C1 | | | D04013P | = C1 | | | ALL | |
| 01CX | | BR | A | 2-6 | 23-12-21 | D00443C | 1 | | | D04013P | = A1 | | | ALL | |
| W1077 | 286T1077 | | | | E2-5 SHELF,C VHF COAX | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-12-31 | D00445C | = C1 | | | D04017P | = C1 | | | ALL | |
| 01CX | | BR | A | 3-0 | 23-12-31 | D00445C | 1 | | | D04017P | = A1 | | | ALL | |
| W1078 | 286T1078 | | | | ELECTRICAL SYSTEMS CARD FILE P50 | | | | | | | | | | |
| 006 | 24 | | PK | 3-0 | 21-28-11 | D04978J | 35 | | | D05209J | 21 | | | 150-154 | |
| 007 | 24 | | PK | 4-0 | 21-51-11 | D04978J | 9 | | | TB0158Y | A004 | BJ | | 050-099, 277-299 | |
| 007 | 24 | | PK | 4-0 | 21-51-11 | D04978J | 9 | | | TB0158G | 3 | 2 | | 150-199, 275-276 | |
| 008 | 24 | | PK | 4-0 | 21-51-21 | D04978J | 5 | | | TB0158Y | C004 | BJ | | 050-099, 277-299 | |
| 008 | 24 | | PK | 4-0 | 21-51-21 | D04978J | 5 | | | TB0158G | 4 | 2 | | 150-199, 275-276 | |
| 010 | 24 | | PK | 3-0 | 31-51-42 | D05209J | 12 | | | TB0182D | A019 | 2 | | ALL | |
| 011 | 24 | | PK | 3-0 | 36-11-51 | D01886 | 55 | | | SM00002 | | W | | ALL | |
| 013 | 24 | | PK | 4-0 | 73-21-17 | TB0182Y | C010 | BJ | | D02160 | 42 | | | 050-099, 150-199 | |
| 013 | 24 | | PK | 4-0 | 73-21-17 | D02160 | 42 | | | TB0182Y | C010 | BJ | | 275-299 | |
| 014 | 24 | | PK | 4-0 | 21-51-11 | D04978J | 22 | | | TB0158Y | C006 | BJ | | ALL | |
| 015 | 24 | | PK | 4-0 | 21-51-11 | D04978J | 20 | | | TB0158Y | A005 | BJ | | ALL | |
| 018 | 24 | | PK | 4-0 | 21-51-11 | D04978J | 17 | | | TB0182D | A023 | 2 | | 050-099 | |
| 018 | 24 | | PK | 3-0 | 21-51-11 | D04978J | 17 | | | TB0182D | A023 | 2 | | 150-199, 275-276 | |
| 018 | 24 | | PK | 3-0 | 21-51-11 | D04978J | 17 | | | TB0182F | A023 | 2 | | 277-299 | |
| 019 | 24 | | PK | 4-0 | 21-51-11 | D04978J | 18 | | | TB0158F | C024 | 2 | | 050-099 | |
| 019 | 24 | | PK | 3-0 | 21-51-11 | D04978J | 18 | | | TB0158F | C024 | 2 | | 150-199, 275-299 | |
| 023 | 24 | | PK | 4-0 | 21-51-11 | D04978J | 36 | | | TB0158F | A012 | 2 | | 050-099, 150-199 | |
| 023 | 24 | | PK | 3-0 | 21-51-11 | D04978J | 36 | | | TB0158F | A012 | 2 | | 275-299 | |
| 027 | 24 | | PK | 4-0 | 73-21-15 | D02160 | 25 | | | D04978J | 49 | | | 050-099, 150-199 | |
| 027 | 24 | | PK | 4-0 | 73-21-15 | D04978J | 49 | | | D02160 | 25 | | | 275-299 | |
| 029 | 24 | | PK | 4-0 | 73-21-15 | D02160 | 24 | | | TB0158G | 10 | 2 | | ALL | |
| 031 | 24 | | PK | 4-0 | 21-51-11 | TB0158Y | A004 | BJ | | D04978J | 16 | | | 050-099, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W1070

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1078 | 286T1078 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 031 | 24 | | PK | 3-0 | 21-51-11 | TB0158G | | 3 | | 2 | | | D04978J | 16 | | | 150-199, 275-276 |
| 032 | 24 | | PK | 4-0 | 21-51-21 | TB0182X | | | D011 | BJ | | | D04978J | 34 | | | 050-099 |
| 032 | 24 | | PK | 3-0 | 21-51-21 | D04978J | | | | | 34 | | TB0182X | D011 | BJ | | 150-199 |
| 032 | 24 | | PK | 3-0 | 21-51-21 | TB0182X | | | D011 | BJ | | | D04978J | 34 | | | 275-299 |
| 034 | 24 | | PK | 3-0 | 21-51-21 | TB0158G | | | | | 9 | 2 | D04978J | 10 | | | 050-099, 150-199 |
| 034 | 24 | | PK | 3-0 | 21-51-11 | TB0158G | | | | | 9 | 2 | D04978J | 10 | | | 275-299 |
| 035 | 24 | | PK | 3-0 | 21-51-11 | D08068J | | | | | 48 | | TB0158Y | C006 | BJ | | 150-199, 275-299 |
| 036 | 24 | | PK | 3-0 | 21-51-21 | TB0158G | | | | | 9 | 2 | D04978J | 23 | | | 050-099, 275-299 |
| 036 | 22 | | PA | 3-0 | 21-51-21 | D04978J | | | | | 23 | | TB0158G | 9 | 2 | | 150-165 |
| 036 | 24 | | PK | 3-0 | 21-51-21 | D04978J | | | | | 23 | | TB0158G | 9 | 2 | | 166-199 |
| 038 | 24 | | PK | 3-0 | 21-51-23 | D03738 | | | | | 24 | | D08068J | 45 | | | ALL |
| 040 | 24 | | PK | 3-0 | 21-25-11 | D03742 | | | | | 1 | | D04978J | 2 | | | ALL |
| 041 | 22 | | PA | 3-0 | 21-25-11 | D03742 | | | | | 3 | | GDX0001 | D.. | 2 | | ALL |
| 042 | 24 | | PK | 3-0 | 21-25-11 | D03742 | | | | | 24 | | D04978J | 1 | | | ALL |
| 043 | 22 | | PA | 3-0 | 21-25-11 | D03742 | | | | | 4 | | GDX0001 | D.. | 2 | | ALL |
| 044 | 24 | | PK | 3-0 | 21-25-11 | D03742 | | | | | 22 | | D04978J | 3 | | | ALL |
| 045 | 24 | | PK | 3-0 | 21-25-11 | D03742 | | | | | 23 | | D04978J | 4 | | | ALL |
| 046 | 24 | | PK | 3-0 | 21-26-11 | D03742 | | | | | 7 | | D08068J | 50 | | | ALL |
| 047 | 22 | | PA | 3-0 | 21-26-11 | D03742 | | | | | 9 | | GDX0001 | D.. | 2 | | ALL |
| 048 | 24 | | PK | 3-0 | 21-26-11 | D03742 | | | | | 28 | | D08068J | 15 | | | ALL |
| 049 | 24 | | PK | 3-0 | 21-26-11 | D03742 | | | | | 8 | | D08068J | 18 | | | ALL |
| 050 | 24 | | PK | 3-0 | 21-26-11 | D03742 | | | | | 6 | | D08068J | 16 | | | ALL |
| 051 | 24 | | PK | 3-0 | 21-26-11 | D03742 | | | | | 27 | | D08068J | 19 | | | ALL |
| 052 | 24 | | PK | 4-0 | 21-26-11 | D03742 | | | | | 36 | | TB0158F | A017 | 2 | | ALL |
| 053 | 24 | | PK | 4-0 | 21-58-14 | D03742 | | | | | 13 | | D08112J | 33 | | | ALL |
| 054 | 22 | | PA | 3-0 | 21-58-14 | D03742 | | | | | 15 | | GDX0001 | D.. | 2 | | ALL |
| 055 | 24 | | PK | 2-0 | 21-58-14 | TB0158G | | | | | 27 | 2 | D08068J | 46 | | | 050-099 |
| 055 | 24 | | PK | 3-0 | 21-58-14 | TB0158Y | | | | | C014 | BJ | D08068J | 46 | | | 150-152, 275-276 |
| 055 | 24 | | PK | 3-0 | 21-58-14 | TB0158Y | | | | | C008 | BJ | D08068J | 46 | | | 153-199 |
| 055 | 24 | | PK | 3-0 | 21-58-14 | TB0158Y | | | | | A002 | BJ | D08068J | 46 | | | 277-299 |
| 056 | 24 | | PK | 3-0 | 21-58-14 | D03742 | | | | | 33 | | D08112J | 10 | | | ALL |
| 057 | 24 | | PK | 3-0 | 21-58-14 | D03742 | | | | | 11 | | D08112J | 8 | | | ALL |
| 058 | 24 | | PK | 3-0 | 21-58-14 | D03742 | | | | | 32 | | D08112J | 11 | | | ALL |
| 059 | 24 | | PK | 4-0 | 21-58-14 | D03742 | | | | | 14 | | TB0158F | C017 | 2 | | ALL |
| 061 | 24 | | PK | 3-0 | 36-11-51 | D01886 | | | | | 5 | | D08112J | 28 | | | ALL |
| 062 | 24 | | PK | 3-0 | 21-26-11 | D03742 | | | | | 35 | | D08112J | 13 | | | ALL |
| 063 | 24 | | PK | 4-0 | 21-58-14 | TB0158F | | | | | C020 | 2 | D03742 | 38 | | | ALL |
| 064 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | | | | 19 | | D04978J | 30 | | | ALL |
| 065 | 22 | | PA | 3-0 | 21-53-22 | D03738 | | | | | 21 | | GDX0001 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1070

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1078 | 286T1078 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | |
| 066 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 6 | | | D04978J | 25 | | | ALL |
| 067 | 24 | | PK | 4-0 | 21-53-22 | D03738 | | 3 | | | TB0182X | C011 | BJ | | ALL |
| 068 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 37 | | | D04978J | 27 | | | ALL |
| 069 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 36 | | | D04978J | 28 | | | ALL |
| 070 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 35 | | | D04978J | 29 | | | ALL |
| 071 | 24 | | PK | 4-0 | 21-53-22 | D03738 | | 8 | | | TB0158F | C012 | 2 | | ALL |
| 072 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 4 | | | D08068J | 12 | | | ALL |
| 073 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 10 | | | D08068J | 13 | | | ALL |
| 074 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 7 | | | D08068J | 10 | | | ALL |
| 075 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 11 | | | D08068J | 11 | | | ALL |
| 076 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 12 | | | D08068J | 8 | | | ALL |
| 077 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 9 | | | D08068J | 9 | | | ALL |
| 078 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 16 | | | D08068J | 6 | | | ALL |
| 079 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 14 | | | D08068J | 5 | | | ALL |
| 080 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 15 | | | D08068J | 4 | | | ALL |
| 081 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 13 | | | D08068J | 3 | | | ALL |
| 082 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 18 | | | D08068J | 2 | | | ALL |
| 083 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 17 | | | D08068J | 1 | | | ALL |
| 084 | 24 | | PK | 3-0 | 21-53-22 | D03738 | | 5 | | | D08068J | 7 | | | ALL |
| 085 | 22 | | PA | 3-0 | 36-11-51 | D01886 | | 60 | | | SM00001 | | W | | ALL |
| 086 | 22 | | PA | 3-0 | 36-11-51 | D01886 | | 40 | | | D08068J | 42 | | | 050-099, 150-199 |
| 086 | 22 | | PA | 4-0 | 36-11-51 | D01886 | | 40 | | | D08068J | 42 | | | 275-299 |
| 087 | 22 | | PA | 3-0 | 36-11-51 | D01886 | | 39 | | | D08068J | 41 | | | 050-099, 150-199 |
| 087 | 22 | | PA | 4-0 | 36-11-51 | D01886 | | 39 | | | D08068J | 41 | | | 275-299 |
| 088 | 24 | | PK | 3-0 | 73-21-18 | D08030J | | 10 | | | TB0182X | A011 | BJ | | ALL |
| 089 | 24 | | PK | 3-0 | 73-21-18 | D08030J | | 12 | | | TB0182Y | C014 | BJ | | 050-099, 162-199, 277-299 |
| 089 | 24 | | PK | 3-0 | 73-21-18 | D08030J | | 12 | | | TB0182Y | A013 | BJ | | 150-157, 275-276 |
| 090 | 24 | | PK | 3-0 | 21-51-11 | D08068J | | 55 | | | TB0158Y | A005 | BJ | | 150-199, 275-299 |
| 092 | 24 | | PK | 3-0 | 36-11-51 | D01886 | | 20 | | | D08068J | 25 | | | 050-099, 150-199 |
| 092 | 24 | | PK | 4-0 | 36-11-51 | D01886 | | 20 | | | D08068J | 25 | | | 275-299 |
| 093 | 22 | | PA | 3-0 | 36-11-51 | D01886 | | 35 | | | D08068J | 22 | | | 050-099, 150-199 |
| 093 | 22 | | PA | 4-0 | 36-11-51 | D01886 | | 35 | | | D08068J | 22 | | | 275-299 |
| 094 | 24 | | PK | 4-0 | 36-11-51 | D01886 | | 53 | | | TB0158Y | C005 | BJ | | ALL |
| 095 | 24 | | PK | 3-0 | 36-11-61 | D01886 | | 28 | | | D08068J | 34 | | | 050-099, 150-199 |
| 095 | 24 | | PK | 4-0 | 36-11-61 | D01886 | | 28 | | | D08068J | 34 | | | 275-299 |
| 097 | 24 | | PK | 3-0 | 36-11-51 | D01886 | | 52 | | | D08068J | 23 | | | 050-099, 150-199 |
| 097 | 24 | | PK | 4-0 | 36-11-51 | D01886 | | 52 | | | D08068J | 23 | | | 275-299 |
| 099 | 22 | | PA | 3-0 | 36-22-11 | D01886 | | 2 | | | D08030J | 44 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1070

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1078 | 286T1078 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | |
| 100 | 22 | | PA | | 3-0 | 36-11-61 | D01886 | | 31 | | | D08068J | | 31 | | 050-099, 150-199 |
| 100 | 22 | | PA | | 4-0 | 36-11-61 | D01886 | | 31 | | | D08068J | | 31 | | 275-299 |
| 101 | 24 | | PK | | 3-0 | 36-11-61 | D01886 | | 1 | | | D08068J | | 35 | | 050-099, 150-199 |
| 101 | 24 | | PK | | 4-0 | 36-11-61 | D01886 | | 1 | | | D08068J | | 35 | | 275-299 |
| 102 | 22 | | PA | | 3-0 | 36-11-61 | D01886 | | 56 | | | D08068J | | 33 | | 050-099, 150-199 |
| 102 | 22 | | PA | | 4-0 | 36-11-61 | D01886 | | 56 | | | D08068J | | 33 | | 275-299 |
| 103 | 24 | | PK | | 3-0 | 36-11-61 | D01886 | | 58 | | | D08068J | | 32 | | 050-099, 150-199 |
| 103 | 24 | | PK | | 4-0 | 36-11-61 | D01886 | | 58 | | | D08068J | | 32 | | 275-299 |
| 104 | 22 | | PA | | 2-0 | 36-11-61 | SM00007 | | | W | | D08068J | | 36 | | ALL |
| 105 | 24 | | PK | | 4-0 | 36-11-41 | D01886 | | 64 | | | TB0248Y | A003 | BJ | | 050-099, 150-199 |
| 105 | 24 | | PK | | 5-0 | 36-11-41 | D01886 | | 64 | | | TB0248Y | A003 | BJ | | 275-299 |
| 106 | 24 | | PK | | 3-0 | 36-11-51 | TB0158Y | | | C005 | BJ | D08068J | | 26 | | ALL |
| 107 | 24 | | PK | | 3-0 | 36-11-51 | TB0158Y | | | C005 | BJ | D08068J | | 29 | | ALL |
| 108 | 22 | | PA | | 2-0 | 21-58-11 | TB0182Y | | | A002 | BJ | D08112J | | 34 | | ALL |
| 109 | 24 | | PV | EI | 3-0 | 73-21-17 | TB0248Y | | | A013 | BJ | D04978J | | 32 | | ALL |
| 109F | 20 | | UA | | 2-0 | 73-21-17 | GD0001 | | | S.. | 2 | D04978J | | | FI | 050-099, 150-199 |
| 109F | 20 | | UA | | 2-0 | 73-21-17 | D04978J | | | | | GD0001 | S.. | 2 | | 275-299 |
| 109Z | | | | EI | 0-0 | 73-21-17 | TB0248Y | | | C014 | BJ | D04978J | | | FI | 050-099, 150-199 |
| 109Z | | | | EI | 0-0 | 73-21-17 | TB0248Y | | | | | D04978J | | | FC | 275-276 |
| 109Z | | | | EI | 0-0 | 73-21-17 | TB0248Y | | | C014 | BJ | D04978J | | | FC | 277-299 |
| 110 | 24 | | PK | | 3-0 | 28-22-12 | D08068J | | 47 | | | TB0248X | D001 | BJ | | ALL |
| 111 | 22 | | PA | | 3-0 | 22-24-11 | D02672 | | 26 | | | D05277J | | 1 | | ALL |
| 112 | 24 | | PK | | 3-0 | 22-12-11 | D02672 | | 22 | | | D05277J | | 22 | | ALL |
| 113 | 24 | | PK | | 3-0 | 22-12-11 | D02672 | | 23 | | | D05277J | | 23 | | ALL |
| 114 | 24 | | PK | | 3-0 | 21-51-21 | D04978J | | 6 | | | TB0182X | D016 | BJ | | 050, 150-154, 275-276 |
| 115 | 22 | | PA | | 4-0 | 27-58-21 | D02672 | | 8 | | | GD0001 | A.. | 2 | | ALL |
| 116 | 24 | | PK | | 3-0 | 21-26-11 | D03742 | | 29 | | | TB0158F | A020 | 2 | | ALL |
| 117 | 24 | | PK | | 3-0 | 27-58-21 | D02672 | | 7 | | | D08030J | | 29 | | ALL |
| 120 | 24 | | PK | | 3-0 | 22-12-11 | D02672 | | 38 | | | D05277J | | 24 | | ALL |
| 121 | 24 | | PK | | 3-0 | 22-12-11 | D02672 | | 39 | | | D05277J | | 25 | | ALL |
| 122 | 22 | | PA | | 3-0 | 73-21-19 | D02672 | | 28 | | | D08030J | | 32 | | ALL |
| 123 | 24 | | PK | | 3-0 | 73-21-19 | D02160 | | 19 | | | TB0248D | C022 | 2 | | 050-099, 150-199 |
| 123 | 24 | | PK | | 4-0 | 73-21-19 | D02160 | | 19 | | | TB0248D | C022 | 2 | | 275-299 |
| 124 | 24 | | PV | EX | 3-0 | 73-21-19 | TB0248Y | | | A013 | BJ | D08030J | | 15 | | ALL |
| 124Z | | | | EX | 0-0 | 73-21-19 | D08030J | | 27 | | | TB0248Y | C014 | BJ | | 050-099, 150-199 |
| 124Z | | | | EX | 0-0 | 73-21-19 | TB0248Y | | | C014 | BJ | D08030J | | 27 | | 275-299 |
| 125 | 22 | | PA | | 3-0 | 73-21-19 | D02160 | | 2 | | | D08030J | | 14 | | 050-099, 150-199 |
| 125 | 22 | | PA | | 4-0 | 73-21-19 | D02160 | | 2 | | | D08030J | | 14 | | 275-299 |
| 126 | 22 | | PA | | 3-0 | 73-21-19 | D02160 | | 35 | | | D08030J | | 31 | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1070

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1078 | 286T1078 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | |
| 126 | 22 | | PA | | 4-0 | 73-21-19 | D02160 | | 35 | | D08030J | | 31 | | 275-299 |
| 127 | 22 | | PA | | 4-0 | 73-21-17 | D02160 | | 64 | | GDX0001 | D.. | 2 | | ALL |
| 130 | 24 | | PK | | 3-0 | 22-32-13 | D02160 | | 62 | | D05277J | | 11 | | 050-099, 150-199 |
| 130 | 24 | | PK | | 4-0 | 22-32-13 | D02160 | | 62 | | D05277J | | 11 | | 275-299 |
| 132 | 20 | | UA | | 4-0 | 73-21-17 | D02160 | | | FC | GDX0001 | S.. | 2 | | 050-099, 150-199 |
| 132 | 20 | | UA | | 4-0 | 73-21-17 | D02160 | | | FA | GDX0001 | S.. | 2 | | 275-276 |
| 132 | 20 | | UA | | 4-0 | 73-21-17 | D02160 | | | FE | GDX0001 | S.. | 2 | | 277-299 |
| 133 | 24 | | PV | FH | 3-0 | 73-21-12 | D02160 | | 8 | | D08030J | | 6 | | 050-099, 150-199 |
| 133 | 24 | | PV | FH | 4-0 | 73-21-12 | D02160 | | 8 | | D08030J | | 6 | | 275-299 |
| 133Z | | | | FH | 0-0 | 73-21-12 | D02160 | | | FD | D08030J | | | FF | 050-099, 150-199 |
| 133Z | | | | FH | 0-0 | 73-21-12 | D02160 | | | FA | D08030J | | | FB | 275-276 |
| 133Z | | | | FH | 0-0 | 73-21-12 | D02160 | | | FE | D08030J | | | FF | 277-299 |
| 134 | 24 | | PK | | 3-0 | 73-21-12 | D02160 | | 7 | | D08030J | | 33 | | 050-099, 150-199 |
| 134 | 24 | | PV | J | 4-0 | 73-21-12 | D02160 | | 7 | | D08030J | | 33 | | 275-276 |
| 134 | 24 | | PK | | 4-0 | 73-21-12 | D02160 | | 7 | | D08030J | | 33 | | 277-299 |
| 134Z | | | | J | 0-0 | 73-21-12 | D02160 | | | FA | D08030J | | | FB | 275-276 |
| 135 | 24 | | PK | | 3-0 | 31-51-42 | D05209J | | 20 | | TB0182D | A026 | 2 | | ALL |
| 136 | 24 | | PK | | 3-0 | 36-11-41 | D08068J | | 30 | | TB0248Y | A003 | BJ | | ALL |
| 138 | 24 | | PV | FM | 3-0 | 73-21-12 | D02160 | | 40 | | D04978J | | 55 | | 050-099, 150-199 |
| 138 | 24 | | PV | FM | 4-0 | 73-21-12 | D02160 | | 40 | | D04978J | | 55 | | 275-299 |
| 138F | 20 | | UA | | 3-0 | 73-21-12 | D02160 | | | FD | GDX0001 | S.. | 2 | | 050-099, 150-199, 277-278 |
| 138F | 20 | | UA | | 4-0 | 73-21-12 | D02160 | | | FD | GDX0001 | S.. | 2 | | 280-299 |
| 138Z | | | | FM | 0-0 | 73-21-12 | D02160 | | | FD | D04978J | | 54 | | 050-099, 150-199, 277-299 |
| 138Z | | | | FM | 0-0 | 73-21-12 | D02160 | | | FA | D04978J | | 54 | | 275-276 |
| 139 | 24 | | PV | FN | 3-0 | 73-21-12 | D02160 | | 41 | | TB0248Z | | 7 | BJ | 050-099, 150-199 |
| 139 | 24 | | PV | FN | 5-0 | 73-21-12 | D02160 | | 41 | | TB0248Z | | 7 | BJ | 275-299 |
| 139Z | | | | FN | 0-0 | 73-21-12 | D02160 | | | FD | TB0248Z | | 8 | BJ | 050-099, 150-199, 277-299 |
| 139Z | | | | FN | 0-0 | 73-21-12 | D02160 | | | FA | TB0248Z | | 8 | BJ | 275-276 |
| 140 | 24 | | PK | | 3-0 | 73-21-17 | D02160 | | 61 | | D08030J | | 36 | | 050-099, 150-199 |
| 140 | 24 | | PK | | 4-0 | 73-21-17 | D02160 | | 61 | | D08030J | | 36 | | 275-299 |
| 141 | 24 | | PK | | 3-0 | 73-21-16 | D02160 | | 54 | | D08030J | | 1 | | 050-099, 150-199 |
| 141 | 24 | | PK | | 4-0 | 73-21-16 | D02160 | | 54 | | D08030J | | 34 | | 275-299 |
| 143 | 24 | | PK | | 3-0 | 22-32-13 | D02160 | | 53 | | D05277J | | 8 | | 050-099, 150-199 |
| 143 | 24 | | PK | | 4-0 | 22-32-13 | D02160 | | 53 | | D05277J | | 8 | | 275-299 |
| 144 | 24 | | PK | | 4-0 | 73-21-17 | D02160 | | 32 | | TB0182X | D012 | BJ | | ALL |
| 145 | 24 | | PK | | 3-0 | 22-32-13 | D02160 | | 30 | | D05277J | | 10 | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1070

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1078 | 286T1078 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 145 | 24 | | PK | 4-0 | 22-32-13 | D02160 | 30 | | | | | | D05277J | 10 | | | 275-299 |
| 146 | 24 | | PK | 3-0 | 73-21-17 | TB0182X | C012 | BJ | | | | | D08030J | 37 | | | ALL |
| 149 | 24 | | PV | FW | 3-0 | 73-21-17 | TB0248Z | 7 | BJ | | | | D08030J | 4 | | | 050-099, 150-199 |
| 149 | 24 | | PV | FX | 3-0 | 73-21-17 | TB0248Z | 7 | BJ | | | | D08030J | 4 | | | 275-299 |
| 149Z | | | | FW | 0-0 | 73-21-17 | TB0248Z | 8 | BJ | | | | D08030J | | | FF | 050-099, 150-199 |
| 149Z | | | | FX | 0-0 | 73-21-17 | TB0248Z | 8 | BJ | | | | D08030J | | | FF | 275-276 |
| 149Z | | | | FX | 0-0 | 73-21-17 | TB0248Z | 8 | BJ | | | | D08030J | | | FF | 277-299 |
| 156 | 24 | | PK | 3-0 | 30-31-11 | D08068J | 51 | | | | | | TB0248Y | C013 | BJ | | ALL |
| 157 | 22 | | PA | 3-0 | 36-11-51 | D08068J | 17 | | | | | | TB0248X | B002 | BJ | | ALL |
| 158 | 24 | | PK | 3-0 | 30-34-11 | D08068J | 52 | | | | | | TB0248X | C002 | BJ | | ALL |
| 160 | 24 | | PK | 3-0 | 73-21-17 | D08030J | 16 | | | | | | TB0182Y | C010 | BJ | | 050-099, 150-199 |
| 160 | 24 | | PK | 3-0 | 73-21-17 | TB0182Y | C010 | BJ | | | | | D08030J | 16 | | | 275-299 |
| 161 | 24 | | PK | 3-0 | 73-21-18 | D08112J | 22 | | | | | | TB0248X | A016 | BJ | | ALL |
| 163 | 24 | | PV | GM | 4-0 | 73-21-17 | D02160 | 6 | | | | | TB0248Z | 7 | BJ | | 050-099, 150-199 |
| 163 | 24 | | PV | GM | 5-0 | 73-21-17 | D02160 | 6 | | | | | TB0248Z | 7 | BJ | | 275-299 |
| 163Z | | | | GM | 0-0 | 73-21-17 | D02160 | | | | | FC | TB0248Z | 8 | BJ | | 050-099, 150-199 |
| 163Z | | | | GM | 0-0 | 73-21-17 | D02160 | | | | | FA | TB0248Z | 8 | BJ | | 275-276 |
| 163Z | | | | GM | 0-0 | 73-21-17 | D02160 | | | | | FE | TB0248Z | 8 | BJ | | 277-299 |
| 165 | 24 | | PK | 3-0 | 22-32-13 | D02160 | 23 | | | | | | D05277J | 9 | | | 050-099, 150-199 |
| 165 | 24 | | PK | 4-0 | 22-32-13 | D02160 | 23 | | | | | | D05277J | 9 | | | 275-299 |
| 167 | 24 | | PK | 4-0 | 73-21-15 | D02160 | 59 | | | | | | TB0182Y | C005 | BJ | | ALL |
| 168 | 24 | | PK | 3-0 | 22-32-13 | D02160 | 26 | | | | | | D05277J | 12 | | | 050-099, 150-199 |
| 168 | 24 | | PK | 4-0 | 22-32-13 | D02160 | 26 | | | | | | D05277J | 12 | | | 275-299 |
| 169 | 24 | | PK | 4-0 | 73-21-15 | D02160 | 65 | | | | | | TB0182Y | A006 | BJ | | ALL |
| 170 | 24 | | PK | 4-0 | 73-21-15 | D02160 | 66 | | | | | | TB0182Y | A003 | BJ | | ALL |
| 176 | 24 | | PK | 3-0 | 36-11-52 | D08112J | 25 | | | | | | TB0248X | A011 | BJ | | ALL |
| 177 | 24 | | PK | 4-0 | 36-11-61 | D08112J | 4 | | | | | | D01886 | 37 | | | ALL |
| 178 | 24 | | PK | 4-0 | 34-61-13 | D02160 | 57 | | | | | | TB0182Y | A005 | BJ | | ALL |
| 179 | 24 | | PK | 4-0 | 34-61-13 | D02160 | 55 | | | | | | TB0182Y | A004 | BJ | | ALL |
| 180 | 24 | | PK | 4-0 | 34-61-13 | D02160 | 29 | | | | | | TB0182Y | A009 | BJ | | ALL |
| 181 | 24 | | PK | 4-0 | 34-61-13 | D02160 | 1 | | | | | | TB0182Y | C009 | BJ | | ALL |
| 182 | 24 | | PK | 4-0 | 34-61-13 | D02160 | 21 | | | | | | TB0182Y | A010 | BJ | | ALL |
| 184 | 24 | | PV | M | 4-0 | 34-61-13 | TB0158Y | A003 | BJ | | | | D05209J | 1 | | | 050-099 |
| 184 | 24 | | PV | M | 3-0 | 34-61-13 | TB0158G | 1 | 2 | | | | D05209J | 1 | | | 150-199 |
| 184 | 24 | | PV | HI | 3-0 | 34-61-13 | TB0158G | 1 | 2 | | | | D05209J | 1 | | | 275-276 |
| 184 | 24 | | PV | HI | 4-0 | 34-61-13 | TB0158Y | A003 | BJ | | | | D05209J | 1 | | | 277-299 |
| 184Z | | | | M | 0-0 | 34-61-13 | TB0158G | DED | | | | | D05209J | DED | | | 050-099, 150-199 |
| 184Z | | | | HI | 0-0 | 34-61-13 | TB0158G | DED | | | | | D05209J | DED | | | 275-276 |
| 184Z | | | | HI | 0-0 | 34-61-13 | TB0158Y | DED | | | | | D05209J | DED | | | 277-299 |

WIRE LIST

D280T132

91-21-11

Section W1070

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1078 | 286T1078 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | |
| 185 | 24 | PV | H | | 3-0 | 34-61-13 | TB0158G | 18 | | 2 | | D05209J | | 2 | | ALL |
| 185Z | | | H | | 0-0 | 34-61-13 | TB0158G | | DED | | | D05209J | | DED | | ALL |
| 186 | 24 | PV | Y | | 3-0 | 34-61-13 | TB0158G | | 21 | 2 | | D05209J | | 3 | | ALL |
| 186Z | | | Y | | 0-0 | 34-61-13 | TB0158G | | DED | | | D05209J | | DED | | ALL |
| 187 | 24 | PV | X | | 3-0 | 34-61-13 | TB0158G | | 22 | 2 | | D05209J | | 4 | | ALL |
| 187Z | | | X | | 0-0 | 34-61-13 | TB0158G | | DED | | | D05209J | | DED | | ALL |
| 188 | 24 | PV | Z | | 3-0 | 34-61-13 | TB0158G | | 23 | 2 | | D05209J | | 5 | | ALL |
| 188Z | | | Z | | 0-0 | 34-61-13 | TB0158G | | DED | | | D05209J | | DED | | ALL |
| 189 | 24 | PK | | | 3-0 | 34-61-13 | TB0182Y | A005 | | BJ | | D05209J | | 6 | | ALL |
| 190 | 24 | PK | | | 3-0 | 34-61-13 | TB0182Y | A004 | | BJ | | D05209J | | 7 | | ALL |
| 191 | 24 | PK | | | 3-0 | 34-61-13 | TB0182Y | A009 | | BJ | | D05209J | | 8 | | ALL |
| 192 | 24 | PK | | | 3-0 | 34-61-13 | TB0182Y | C009 | | BJ | | D05209J | | 9 | | ALL |
| 193 | 24 | PK | | | 3-0 | 34-61-13 | TB0182Y | A010 | | BJ | | D05209J | | 10 | | ALL |
| 194 | 24 | PK | | | 4-0 | 27-58-21 | D02672 | | 29 | | | TB0248D | C017 | 2 | | ALL |
| 195 | 24 | PK | | | 3-0 | 36-11-62 | D08112J | | 5 | | | TB0248X | B011 | BJ | | ALL |
| 197 | 22 | PA | | | 3-0 | 27-58-21 | D02672 | | 43 | | | GDX0001 | D.. | 2 | | ALL |
| 198 | 22 | PA | | | 3-0 | 27-61-11 | TB0248D | A018 | | 2 | | D05277J | | 16 | | ALL |
| 201B | 24 | PL | A | | 3-0 | 27-58-31 | D02672 | | 18 | | | D08030J | | 20 | | ALL |
| 201R | 24 | PL | A | | 0-0 | 27-58-31 | D02672 | | 17 | | | D08030J | | 21 | | ALL |
| 202B | 24 | PL | B | | 3-0 | 22-32-13 | D02672 | | 21 | | | D05277J | | 21 | | ALL |
| 202R | 24 | PL | B | | 0-0 | 22-32-13 | D02672 | | 19 | | | D05277J | | 20 | | ALL |
| 203B | 24 | PL | D | | 3-0 | 27-58-21 | D02672 | | 9 | | | D08030J | | 22 | | ALL |
| 203R | 24 | PL | D | | 0-0 | 27-58-21 | D02672 | | 10 | | | D08030J | | 23 | | ALL |
| 204B | 22 | PB | E | | 3-0 | 27-41-11 | D02672 | | 41 | | | D05277J | | 5 | | ALL |
| 204R | 22 | PB | E | | 0-0 | 27-41-11 | D02672 | | 40 | | | D05277J | | 4 | | ALL |
| 207B | 24 | PL | AC | | 3-0 | 27-51-31 | TB0158F | A019 | | 2 | | D08030J | | 18 | | ALL |
| 207R | 24 | PL | AC | | 0-0 | 27-51-31 | TB0158F | C019 | | 2 | | D08030J | | 19 | | ALL |
| 208B | 24 | PL | AA | | 3-0 | 27-58-21 | D02672 | | 35 | | | D05277J | | 32 | | ALL |
| 208R | 24 | PL | AA | | 0-0 | 27-58-21 | D02672 | | 31 | | | D05277J | | 33 | | ALL |
| 211B | 24 | PW | IK | | 3-0 | 77-12-12 | D08030J | | 40 | | | TB0182Y | C018 | BJ | | 050-099, 162-199, 277-299 |
| 211B | 24 | PW | IK | | 3-0 | 77-12-12 | D08030J | | 40 | | | TB0158Y | C026 | BJ | | 150-157, 275-276 |
| 211R | 24 | PW | IK | | 0-0 | 77-12-12 | D08030J | | 38 | | | TB0182Y | A018 | BJ | | 050-099, 162-199, 277-299 |
| 211R | 24 | PW | IK | | 0-0 | 77-12-12 | D08030J | | 38 | | | TB0158Y | A026 | BJ | | 150-157, 275-276 |
| 211Z | | | IK | | 0-0 | 77-12-12 | D08030J | | 39 | | | TB0182Y | REF | | FH | 050-099, 162-199, 277-299 |
| 211Z | | | IK | | 0-0 | 77-12-12 | D08030J | | 39 | | | TB0158Z | | 28 | BJ | 150-157, 275-276 |
| 240 | 22 | PA | | | 3-0 | 36-11-61 | D08112J | | 36 | | | D01886 | | 27 | | 050-099, 150-199 |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1078 | 286T1078 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 240 | 22 | | PA | | 4-0 | 36-11-61 | D08112J | | 36 | | | | D01886 | 27 | | | 275-299 |
| 241 | 22 | | PA | | 3-0 | 36-11-61 | D08112J | | 37 | | | | D01886 | 61 | | | 050-099, 150-199 |
| 241 | 22 | | PA | | 4-0 | 36-11-61 | D08112J | | 37 | | | | D01886 | 61 | | | 275-299 |
| 242 | 24 | | PK | | 3-0 | 36-11-61 | D08112J | | 38 | | | | D01886 | 47 | | | 050-099, 150-199 |
| 242 | 24 | | PK | | 4-0 | 36-11-61 | D08112J | | 38 | | | | D01886 | 47 | | | 275-299 |
| 243 | 24 | | PK | | 3-0 | 36-11-61 | D08112J | | 39 | | | | D01886 | 18 | | | 050-099, 150-199 |
| 243 | 24 | | PK | | 4-0 | 36-11-61 | D08112J | | 39 | | | | D01886 | 18 | | | 275-299 |
| 246 | 24 | | PK | | 3-0 | 36-11-61 | D08112J | | 23 | | | | D01886 | 65 | | | 050-099, 150-199 |
| 246 | 24 | | PK | | 4-0 | 36-11-61 | D08112J | | 23 | | | | D01886 | 65 | | | 275-299 |
| 247 | 24 | | PK | | 3-0 | 36-11-62 | D08112J | | 24 | | | | TB0248X | D011 | BJ | | ALL |
| 248 | 22 | | PA | | 3-0 | 36-11-61 | D01886 | | 66 | | | | SM00007 | | W | | 050-099, 150-199 |
| 248 | 22 | | PA | | 3-0 | 36-11-61 | SM00007 | | | W | | | D01886 | 66 | | | 275-299 |
| 249 | 22 | | PA | | 3-0 | 36-11-61 | D01886 | | 34 | | | | SM00007 | | W | | 050-099, 150-199 |
| 249 | 22 | | PA | | 3-0 | 36-11-61 | SM00007 | | | W | | | D01886 | 34 | | | 275-299 |
| 250B | 24 | | PW | IO | 3-0 | 77-12-12 | D08112J | | 42 | | | | TB0182Y | C018 | BJ | | 050-099, 162-199 |
| 250B | 24 | | PW | IO | 3-0 | 77-12-12 | D08112J | | 42 | | | | TB0158Y | C026 | BJ | | 150-157 |
| 250B | 24 | | PW | JY | 3-0 | 77-12-12 | D08112J | | 42 | | | | TB0158Y | C026 | BJ | | 275-276 |
| 250B | 24 | | PW | JY | 3-0 | 77-12-12 | D08112J | | 42 | | | | TB0182Y | C018 | BJ | | 277-299 |
| 250R | 24 | | PW | IO | 0-0 | 77-12-12 | D08112J | | 41 | | | | TB0182Y | A018 | BJ | | 050-099, 162-199 |
| 250R | 24 | | PW | IO | 0-0 | 77-12-12 | D08112J | | 41 | | | | TB0158Y | A026 | BJ | | 150-157 |
| 250R | 24 | | PW | JY | 0-0 | 77-12-12 | D08112J | | 41 | | | | TB0158Y | A026 | BJ | | 275-276 |
| 250R | 24 | | PW | JY | 0-0 | 77-12-12 | D08112J | | 41 | | | | TB0182Y | A018 | BJ | | 277-299 |
| 250Z | | | | IO | 0-0 | 77-12-12 | D08112J | | 43 | | | | TB0182Y | REF | | FH | 050-099, 162-199 |
| 250Z | | | | IO | 0-0 | 77-12-12 | D08112J | | 43 | | | | TB0158Z | 28 | BJ | | 150-157 |
| 250Z | | | | JY | 0-0 | 77-12-12 | D08112J | | 43 | | | | TB0158Z | 28 | BJ | | 275-276 |
| 250Z | | | | JY | 0-0 | 77-12-12 | D08112J | | 43 | | | | TB0182Y | REF | | FH | 277-299 |
| 251 | 24 | | PK | | 3-0 | 36-11-61 | D08112J | | 40 | | | | D01886 | 17 | | | 050-099, 150-199 |
| 251 | 24 | | PK | | 4-0 | 36-11-61 | D08112J | | 40 | | | | D01886 | 17 | | | 275-299 |
| 252 | 22 | | PA | | 1-0 | 36-11-51 | D08068J | | 44 | | | | SM00001 | | W | | 050-099, 150-199 |
| 252 | 22 | | PA | | 2-0 | 36-11-51 | SM00001 | | | W | | | D08068J | 44 | | | 275-299 |
| 301B | 24 | | PM | C | 3-0 | 27-58-21 | D02672 | | 12 | | | | D08030J | 24 | | | ALL |
| 301R | 24 | | PM | C | 0-0 | 27-58-21 | D02672 | | 13 | | | | D08030J | 25 | | | ALL |
| 301Y | 24 | | PM | C | 0-0 | 27-58-21 | D02672 | | 11 | | | | D08030J | 26 | | | ALL |
| 302B | 24 | | PM | AB | 3-0 | 27-58-21 | D02672 | | 32 | | | | D05277J | 29 | | | ALL |
| 302R | 24 | | PM | AB | 0-0 | 27-58-21 | D02672 | | 33 | | | | D05277J | 30 | | | ALL |
| 302Y | 24 | | PM | AB | 0-0 | 27-58-21 | D02672 | | 34 | | | | D05277J | 31 | | | ALL |
| 500 | 24 | | PK | | 4-0 | 21-51-11 | D04978J | | 21 | | | | D01886 | 38 | | | ALL |
| 502 | 24 | | PK | | 4-0 | 21-51-11 | D04978J | | 15 | | | | TB0182X | A016 | BJ | | 050-099 |
| 502 | 24 | | PK | | 3-0 | 21-51-11 | D04978J | | 15 | | | | TB0182X | A016 | BJ | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1070

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1078 | 286T1078 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | |
| 503 | 24 | | PK | 4-0 | 21-51-21 | TB0182X | B016 | BJ | | D01886 | | 4 | | ALL | |
| 505 | 24 | | PK | 4-0 | 73-21-15 | D02160 | | 33 | | TB0158Y | A006 | BJ | | 050-099, 153-199 | |
| 505 | 24 | | PK | 4-0 | 73-21-15 | D02160 | | 33 | | TB0158Y | A014 | BJ | | 150-152, 275-276 | |
| 505 | 24 | | PK | 5-0 | 73-21-15 | D02160 | | 33 | | TB0158Y | A006 | BJ | | 277-299 | |
| 506 | 24 | | PK | 3-0 | 34-61-13 | TB0158Y | A006 | BJ | | D05209J | | 11 | | 050-099, 153-199, 280-299 | |
| 506 | 24 | | PK | 3-0 | 34-61-13 | TB0158Y | A014 | BJ | | D05209J | | 11 | | 150-152, 275-276 | |
| 506 | 24 | | PK | 4-0 | 34-61-13 | TB0158Y | A006 | BJ | | D05209J | | 11 | | 277-278 | |
| 507R | 22 | | PH | 3-0 | 26-18-12 | D04978J | | 42 | | D01886 | | 36 | | 050-099, 150-199 | |
| 507R | 22 | | PH | 4-0 | 26-18-12 | D04978J | | 42 | | D01886 | | 36 | | 275-299 | |
| 508R | 22 | | PH | 3-0 | 26-18-12 | D04978J | | 43 | | D01886 | | 57 | | 050-099, 150-199 | |
| 508R | 22 | | PH | 4-0 | 26-18-12 | D04978J | | 43 | | D01886 | | 57 | | 275-299 | |
| 509 | 24 | | PK | 3-0 | 21-24-11 | D08068J | | 39 | | TB0182X | A015 | BJ | | 050-099, 150-199 | |
| 510 | 24 | | PK | 3-0 | 21-24-11 | D08068J | | 43 | | TB0182X | D015 | BJ | | 050-099, 150-199 | |
| 512 | 24 | | PK | 3-0 | 21-24-11 | D08068J | | 53 | | TB0182X | C015 | BJ | | 050-099, 150-199 | |
| 513 | 22 | | PA | 3-0 | 21-24-11 | D08068J | | 54 | | TB0182X | B015 | BJ | | 050-099, 150-199 | |
| 514 | 24 | | PK | 3-0 | 21-24-11 | D08068J | | 37 | | TB0248Y | A010 | BJ | | 050-099, 150-199 | |
| 515 | 24 | | PK | 3-0 | 21-24-11 | D08068J | | 38 | | TB0248Y | A010 | BJ | | 050-099, 150-199 | |
| 517 | 24 | | PK | 3-0 | 21-58-11 | TB0248X | A002 | BJ | | D04978J | | 13 | | ALL | |
| 518 | 24 | | PK | 4-0 | 21-51-11 | D04978J | | 33 | | TB0182X | B012 | BJ | | 050-099 | |
| 518 | 24 | | PK | 3-0 | 21-51-11 | D04978J | | 33 | | TB0182X | B012 | BJ | | 150-199, 275-299 | |
| 520 | 24 | | PK | 2-0 | 27-58-21 | TB0248D | C017 | 2 | | TB0248D | C018 | 2 | | ALL | |
| 521 | 24 | | PK | 3-0 | 34-46-12 | TB0248D | A017 | 2 | | D05277J | | 28 | | ALL | |
| 522 | 22 | | PA | 3-0 | 34-45-13 | D05209J | | 22 | | TB0158D | A014 | 2 | | 153-154 | |
| 523 | 24 | | PV | 2-0 | 73-21-11 | D08030J | | 2 | | TB0182X | C027 | BJ | | 050-099, 150-199 | |
| 523 | 24 | | PV | 3-0 | 73-21-11 | D08030J | | 2 | | TB0182X | C027 | BJ | | 275-299 | |
| 523Z | | | | 0-0 | 73-21-11 | D08030J | | | M4 | TB0182X | D027 | BJ | | ALL | |
| 524 | 24 | | PK | 2-0 | 21-58-12 | D04978J | | 8 | | TB0182X | A028 | BJ | | ALL | |
| 525 | 24 | | PK | 2-0 | 21-58-12 | D04978J | | 14 | | TB0182X | B028 | BJ | | ALL | |
| 526 | 24 | | PK | 2-0 | 21-58-12 | D04978J | | 37 | | TB0182X | C028 | BJ | | ALL | |
| 527 | 24 | | PK | 3-0 | 21-58-14 | D03742 | | 12 | | TB0158G | | 27 | 2 | 050-099 | |
| 527 | 24 | | PK | 3-0 | 21-58-14 | D03742 | | 12 | | TB0158Y | C014 | BJ | | 150-152 | |
| 527 | 24 | | PK | 3-0 | 21-58-14 | D03742 | | 12 | | TB0158Y | C008 | BJ | | 153-199 | |
| 527 | 24 | | PK | 4-0 | 21-58-14 | D03742 | | 12 | | TB0158Y | C014 | BJ | | 275-276 | |
| 527 | 24 | | PK | 4-0 | 21-58-14 | D03742 | | 12 | | TB0158Y | A002 | BJ | | 277-299 | |
| 528R | 22 | | PH | 3-0 | 26-18-12 | D04978J | | 44 | | D01886 | | 6 | | 050-099, 150-199 | |
| 528R | 22 | | PH | 4-0 | 26-18-12 | D04978J | | 44 | | D01886 | | 6 | | 275-299 | |
| 529R | 22 | | PU | 4-0 | 26-18-22 | D08112J | | 21 | | SP03260 | | | S | 050-099, 275-299 | |
| 529R | 22 | | PH | 3-0 | 26-18-22 | D08112J | | 21 | | TB0248X | C001 | BJ | | 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W1070

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1078 | 286T1078 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 529Z | | | VD | 0-0 | 26-18-22 | D08112J | DED | | | | | | SP03260 | DED | | | 050-099, 275-299 |
| 532 | 24 | PK | | 2-0 | 21-58-12 | D04978J | 48 | | | | | | TB0182X | D028 | BJ | | ALL |
| 535 | 24 | PV | BJ | 3-0 | 73-21-17 | D08030J | 7 | | | | | | TB0248Z | 7 | BJ | | 050-099, 150-199 |
| 535 | 24 | PV | WT | 3-0 | 73-21-17 | TB0248Z | 7 | BJ | | | | | D08030J | 7 | | | 275-299 |
| 535Z | | | BJ | 0-0 | 73-21-17 | D08030J | 8 | | | | | | TB0248Z | 8 | BJ | | 050-099, 150-199 |
| 535Z | | | WT | 0-0 | 73-21-17 | TB0248Z | 8 | BJ | | | | | D08030J | 8 | | | 275-299 |
| 544JA | 24 | PV | VS | 2-0 | 73-21-17 | TB0248Y | A013 | BJ | | | | | TB0248Z | 7 | BJ | | 050-099, 150-199 |
| 544JA | 24 | PV | JA | 3-0 | 73-21-17 | TB0248Y | A013 | BJ | | | | | TB0248Z | 7 | BJ | | 275-276, 280-299 |
| 544JA | 24 | PV | VS | 3-0 | 73-21-17 | TB0248Y | A013 | BJ | | | | | TB0248Z | 7 | BJ | | 277-278 |
| 544Z | | | VS | 0-0 | 73-21-17 | TB0248Y | C014 | BJ | | | | | TB0248Z | 8 | BJ | | 050-099, 150-199, 277-278 |
| 544Z | | | JA | 0-0 | 73-21-17 | TB0248Y | | | | | FY | | TB0248Z | 8 | BJ | | 275-276 |
| 544Z | | | JA | 0-0 | 73-21-17 | TB0248Y | C014 | BJ | | | | | TB0248Z | 8 | BJ | | 280-299 |
| 558 | 22 | PA | | 3-0 | 34-45-13 | D05209J | 24 | | | | | | TB0158D | A014 | 2 | | 050-099, 155-156, 162-166 |
| 558 | 22 | PA | | 3-0 | 34-45-13 | D05209J | 24 | | | | | | TB0182D | A024 | 2 | | 150-152 |
| 600 | 22 | PA | | 3-0 | 27-41-11 | D02672 | 44 | | | | | | D05277J | 15 | | | ALL |
| 609 | 24 | PV | YI | 3-0 | 73-21-17 | D08030J | 9 | | | | | | TB0248Z | 7 | BJ | | ALL |
| 609Z | | | YI | 0-0 | 73-21-17 | D08030J | | | | | FF | | TB0248Z | 8 | BJ | | 050-099, 150-199, 277-299 |
| 609Z | | | YI | 0-0 | 73-21-17 | D08030J | | | | | FB | | TB0248Z | 8 | BJ | | 275-276 |
| 618 | 24 | PK | | 3-0 | 73-21-18 | D08030J | 50 | | | | | | TB0248X | D016 | BJ | | 050-099, 150-199, 277-299 |
| 618 | 24 | PK | | 5-0 | 73-21-18 | D08030J | 50 | | | | | | TB0248X | D016 | BJ | | 275-276 |
| 621 | 22 | PA | | 3-0 | 21-66-11 | TB0248Y | C010 | BJ | | | | | D04978J | 53 | | | 050-099, 162-199 |
| 700 | 24 | PK | | 4-0 | 31-31-21 | D05209J | 18 | | | | | | D02672 | 14 | | | 050-099, 150-199 |
| 700 | 24 | PK | | 4-0 | 31-31-21 | D02672 | 14 | | | | | | D05209J | 18 | | | 275-299 |
| 701 | 24 | PK | | 3-0 | 36-22-11 | D08112J | 6 | | | | | | TB0248Y | C009 | BJ | | ALL |
| 702 | 22 | PA | | 2-0 | 36-22-11 | D08030J | 41 | | | | | | SM00008 | | W | | ALL |
| 703 | 24 | PK | | 2-0 | 36-22-11 | D08112J | 9 | | | | | | SM00008 | | W | | ALL |
| 708 | 24 | PK | | 3-0 | 21-51-21 | D08112J | 19 | | | | | | TB0158G | 16 | 2 | | ALL |
| 709 | 24 | PK | | 3-0 | 21-51-21 | D08112J | 20 | | | | | | TB0182Y | C001 | BJ | | ALL |
| 718 | 24 | PK | | 3-0 | 21-25-11 | D03742 | 25 | | | | | | D04978J | 12 | | | ALL |
| 720 | 24 | PK | | 3-0 | 21-58-11 | D08112J | 32 | | | | | | TB0182Y | A001 | BJ | | ALL |
| 721 | 24 | PK | | 4-0 | 31-31-21 | D05209J | 19 | | | | | | D02672 | 16 | | | 050-099, 150-199 |
| 721 | 24 | PK | | 4-0 | 31-31-21 | D02672 | 16 | | | | | | D05209J | 19 | | | 275-299 |
| 722 | 24 | PK | | 3-0 | 21-58-14 | D08112J | 1 | | | | | | D03742 | 37 | | | ALL |
| 724 | 24 | PK | | 3-0 | 21-58-15 | D08112J | 3 | | | | | | TB0248X | A012 | BJ | | ALL |
| 725 | 24 | PK | | 3-0 | 21-25-11 | D03742 | 2 | | | | | | TB0248D | A019 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1070

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|---------|-------|------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1078 | 286T1078 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | |
| 726 | 24 | | PK | | 2-0 | 21-25-11 | TB0248Y | C010 | BJ | | TB0248D | C019 | 2 | | ALL |
| 727 | 24 | | PK | | 3-0 | 21-25-11 | TB0248Y | C010 | BJ | | D04978J | 7 | | | ALL |
| 728 | 24 | | PK | | 3-0 | 21-26-11 | TB0248X | C011 | BJ | | D08112J | 12 | | | ALL |
| 737 | 24 | | PK | | 3-0 | 36-11-51 | D01886 | | 54 | | SM00002 | | W | | ALL |
| 738 | 22 | | PA | | 3-0 | 36-11-51 | D01886 | | 11 | | D08068J | 28 | | | 050-099, 150-199 |
| 738 | 22 | | PA | | 4-0 | 36-11-51 | D01886 | | 11 | | D08068J | 28 | | | 275-299 |
| 739 | 22 | | PA | | 3-0 | 36-11-51 | D01886 | | 59 | | SM00001 | | W | | ALL |
| 740 | 22 | | PA | | 3-0 | 36-11-51 | D08068J | | 24 | | SM00001 | | W | | ALL |
| 741 | 24 | | PK | | 3-0 | 36-11-51 | D08068J | | 40 | | SM00002 | | W | | ALL |
| 744 | 22 | | PA | | 3-0 | 36-11-51 | D01886 | | 46 | | D08068J | 27 | | | 050-099, 150-199 |
| 744 | 22 | | PA | | 4-0 | 36-11-51 | D01886 | | 46 | | D08068J | 27 | | | 275-299 |
| 749 | 24 | | PK | | 4-0 | 21-58-11 | D04978J | | 26 | | TB0248X | A001 | BJ | | ALL |
| 752 | 22 | | PA | | 3-0 | 36-22-11 | SM00008 | | | W | D01886 | 3 | | | ALL |
| 763 | 24 | | PV | M3 | 3-0 | 73-21-11 | TB0182Y | A007 | BJ | | D04978J | 41 | | | 050-099, 150-199 |
| 763 | 24 | | PV | MK | 3-0 | 73-21-11 | TB0182Y | A007 | BJ | | D04978J | 41 | | | 275-299 |
| 763Z | | | | M3 | 0-0 | 73-21-11 | TB0182Y | C007 | BJ | | D04978J | 40 | | | 050-099, 150-199 |
| 763Z | | | | MK | 0-0 | 73-21-11 | TB0182Y | C007 | BJ | | D04978J | 40 | | | 275-299 |
| 764 | 24 | | PV | M4 | 3-0 | 73-21-11 | D08030J | | 46 | | TB0248Z | 7 | BJ | | 050-099, 150-199 |
| 764 | 24 | | PV | AE | 3-0 | 73-21-11 | D08030J | | 46 | | TB0248Z | 7 | BJ | | 275-299 |
| 764Z | | | | M4 | 0-0 | 73-21-11 | D08030J | | | M4 | TB0248Z | 8 | BJ | | 050-099, 150-199 |
| 764Z | | | | AE | 0-0 | 73-21-11 | D08030J | | | M4 | TB0248Z | 8 | BJ | | 275-299 |
| 766 | 24 | | PK | | 3-0 | 27-51-31 | D08030J | | 11 | | TB0158F | A024 | 2 | | ALL |
| 767 | 24 | | PK | | 4-0 | 27-58-31 | D08030J | | 42 | | D02672 | 52 | | | ALL |
| 778 | 24 | | PK | | 4-0 | 73-21-15 | D02160 | | 27 | | TB0248X | C012 | BJ | | ALL |
| 779 | 22 | | PA | | 2-0 | 73-21-19 | D08030J | | 43 | | TB0248D | C022 | 2 | | 050-099, 150-199 |
| 779 | 22 | | PA | | 3-0 | 73-21-19 | TB0248D | C022 | 2 | | D08030J | 43 | | | 275-299 |
| 780 | 22 | | PA | | 2-0 | 73-21-19 | D08030J | | 17 | | TB0248D | A022 | 2 | | 050-099, 150-199 |
| 780 | 22 | | PA | | 3-0 | 73-21-19 | TB0248D | A022 | 2 | | D08030J | 17 | | | 275-299 |
| 781 | 22 | | PA | | 2-0 | 36-11-51 | D08068J | | 49 | | SM00001 | | W | | 156, 166 |
| 901 | 24 | | PK | | 3-0 | 21-58-11 | D08112J | | 18 | | TB0182X | B011 | BJ | | ALL |
| FRA | | | | | 0-0 | 73-21-11 | D08030J | | 48 | | D08030J | | | M4 | 050-099, 150-199 |
| FRB | | | | | 0-0 | 73-21-17 | D08030J | | 13 | | D08030J | | | FB | 275-276 |
| FRB | | | | | 0-0 | 73-21-17 | D08030J | | 13 | | D08030J | | | FF | 277-278 |
| FRD | | | | | 0-0 | 73-21-17 | D08030J | | 13 | | D08030J | | | FF | 050-099, 150-199 |
| FRF | | | | | 0-0 | 73-21-17 | D08030J | | 13 | | D08030J | | | FF | 280-299 |
| FRH | | | | | 0-0 | 77-12-12 | TB0182Y | A017 | BJ | | TB0182Y | REF | | FH | 050-099, 162-199, 277-299 |
| FRM | | | | | 0-0 | 73-21-11 | D08030J | | 48 | | D08030J | | | M4 | 275-299 |
| FRY | | | | | 0-0 | 73-21-17 | TB0248Y | | | FY | TB0248Y | C014 | BJ | | 275-276 |

WIRE LIST

D280T132

91-21-11

Section W1070

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|--------|-------|------|---------|--------|-------------|---------------------------------------|
| | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | |
| W1078 | 286T1078 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | |
| PA1 | | | | | 0-0 | 99-99-99 | D03742 | | 26 | | D03742 | | 34 | ALL |
| PC1 | | | | | 0-0 | 99-99-99 | D03738 | | 22 | | D03738 | | 38 | ALL |
| PD1 | | | | | 0-0 | 36-11-51 | D01886 | | 41 | | D01886 | | 63 | 050-099, 150-156, 162-166, 275-276 |
| PD1 | | | | | 0-0 | 36-11-51 | D01886 | | 9 | | D01886 | | 51 | 157, 167-199, 277-299 |
| PE1 | | | | | 0-0 | 27-58-21 | D02672 | | 47 | | D02672 | | 66 | 050-099, 150-154 |
| PE1 | | | | | 0-0 | 27-58-21 | D02672 | | 47 | | D02672 | | 64 | 155-199, 275-299 |
| PF1 | | | | | 0-0 | 73-21-15 | D02160 | | 11 | | D02160 | | 20 | ALL |
| W1079 | 286T1079 | | | E2-6 SHELF, HF-L COAX | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-11-11 | D00641B | | = C71 | | D04001P | | = C1 | ALL |
| 01CX | | 65 | | A | 4-0 | 23-11-11 | D00641B | | 71 | | D04001P | | = A1 | ALL |

WIRE LIST
D280T132

91-21-11
Section W1070
Page 12 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1080 | 286T1080 | | | ELECTRICAL SYSTEMS CARD FILE P50 | | | | | | | | | | | |
| 001 | 24 | | PK | | 3-0 | 21-51-21 | D01868 | 19 | | | D05552J | 18 | | | 050-099, 150-199 |
| 001 | 24 | | PK | | 3-0 | 21-51-21 | TB0158Y | C008 | BJ | | D05552J | 18 | | | 275-299 |
| 002 | 22 | | PA | | 4-0 | 21-51-21 | D01868 | 21 | | | GDX0002 | D.. | 2 | | ALL |
| 003 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 13 | | | TB0182X | D016 | BJ | | 050, 150-154, 275-276 |
| 004 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 14 | | | D05552J | 6 | | | ALL |
| 005 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 8 | | | D05552J | 7 | | | ALL |
| 006 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 7 | | | D05552J | 8 | | | ALL |
| 007 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 36 | | | TB0158Y | C004 | BJ | | 050-099, 277-299 |
| 007 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 36 | | | TB0158G | 4 | 2 | | 150-199, 275-276 |
| 008 | 24 | | PK | | 4-0 | 21-51-11 | D01868 | 15 | | | TB0158Y | A004 | BJ | | 050-099, 277-299 |
| 008 | 24 | | PK | | 4-0 | 21-51-11 | D01868 | 15 | | | TB0158G | 3 | 2 | | 150-199, 275-276 |
| 009 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 17 | | | D08032J | 38 | | | ALL |
| 010 | 24 | | PK | | 3-0 | 31-51-41 | TB0158Y | C008 | BJ | | D04809J | 12 | | | 050-099 |
| 010 | 24 | | PK | | 3-0 | 31-51-41 | TB0248X | B001 | BJ | | D04809J | 12 | | | 150-199, 275-299 |
| 011 | 22 | | PA | | 3-0 | 36-11-52 | D01876 | 39 | | | D05766J | 13 | | | ALL |
| 012 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 19 | | | TB0158Y | C008 | BJ | | 275-299 |
| 013 | 24 | | PK | | 2-0 | 21-51-21 | D05552J | 25 | | | TB0158Y | A008 | BJ | | 150-199, 275-299 |
| 014 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 4 | | | TB0158Y | A008 | BJ | | ALL |
| 015 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 5 | | | TB0158Y | C007 | BJ | | ALL |
| 016 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 22 | | | D05552J | 21 | | | ALL |
| 017 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 1 | | | D05552J | 22 | | | ALL |
| 018 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 27 | | | TB0182D | A021 | 2 | | 050-099, 150-199, 275-276 |
| 018 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 27 | | | D02676 | 24 | | | 277-278 |
| 018 | 24 | | PK | | 2-0 | 21-51-21 | D01868 | 27 | | | D02676 | 24 | | | 280-299 |
| 019 | 24 | | PK | | 3-0 | 21-51-21 | D01868 | 6 | | | D02676 | 27 | | | ALL |
| 01A | 24 | | PK | | 4-0 | 21-26-11 | TB0158F | A017 | 2 | | D05644J | 27 | | | 156-157, 166-199, 277-299 |
| 020 | 22 | | PA | | 4-0 | 21-51-21 | D01868 | 28 | | | TB0182Y | C001 | BJ | | ALL |
| 021 | 24 | | PK | | 4-0 | 21-25-21 | D01868 | 31 | | | D05552J | 27 | | | ALL |
| 022 | 24 | | PK | | 4-0 | 21-53-21 | D01868 | 9 | | | D08032J | 46 | | | ALL |
| 023 | 24 | | PK | | 4-0 | 21-53-22 | D01868 | 26 | | | TB0158F | C012 | 2 | | ALL |
| 024 | 24 | | PK | | 2-0 | 21-51-21 | D05552J | 31 | | | TB0158Y | C007 | BJ | | 150-199, 275-299 |
| 025 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 2 | | | D05552J | 4 | | | ALL |
| 026 | 24 | | PK | | 3-0 | 73-21-15 | D01868 | 32 | | | D05552J | 54 | | | ALL |
| 027 | 24 | | PK | | 3-0 | 73-21-15 | D02162 | 25 | | | D01868 | 18 | | | 050-099, 150-199 |
| 027 | 24 | | PK | | 3-0 | 73-21-15 | D01868 | 18 | | | D02162 | 25 | | | 275-299 |
| 028 | 22 | | PA | | 4-0 | 21-51-21 | D01868 | 10 | | | TB0158G | 16 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1080
Page 1
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1080 | 286T1080 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 029 | 24 | | PK | 4-0 | 21-26-11 | D01874 | | 29 | | | | | TB0158F | A017 | 2 | | 050-099, 150-155, 162-165, 275-276 |
| 029 | 24 | | PK | 4-0 | 21-26-11 | D01874 | | 29 | | | | | D05644J | | 26 | | 156-157, 166-199, 277-299 |
| 030 | 24 | | PK | 4-0 | 21-51-21 | D01868 | | 12 | | | | | TB0182X | D011 | BJ | | ALL |
| 032 | 22 | | PA | 3-0 | 21-51-21 | TB0182Y | | C001 | | BJ | | | D05552J | | 24 | | ALL |
| 033 | 24 | | PK | 3-0 | 36-11-41 | D01876 | | 64 | | | | | TB0248Y | A003 | BJ | | 050-099, 150-199 |
| 033 | 24 | | PK | 4-0 | 36-11-41 | D01876 | | 64 | | | | | TB0248Y | A003 | BJ | | 275-299 |
| 034 | 22 | | PA | 3-0 | 21-51-21 | TB0158G | | 16 | | 2 | | | D05552J | | 23 | | ALL |
| 035 | 24 | | PK | 4-0 | 21-25-21 | D01874 | | 1 | | | | | D05552J | | 29 | | ALL |
| 036 | 22 | | PA | 4-0 | 21-25-21 | D01874 | | 3 | | | | | GD0002 | D.. | 2 | | ALL |
| 037 | 24 | | PK | 4-0 | 21-25-21 | D01874 | | 24 | | | | | D05552J | | 26 | | ALL |
| 038 | 22 | | PA | 4-0 | 21-25-21 | D01874 | | 4 | | | | | GD0004 | D.. | 2 | | ALL |
| 039 | 24 | | PK | 4-0 | 21-25-21 | D01874 | | 22 | | | | | D05552J | | 28 | | ALL |
| 040 | 24 | | PK | 4-0 | 21-25-21 | D01874 | | 23 | | | | | D05552J | | 30 | | ALL |
| 041 | 24 | | PK | 3-0 | 21-58-15 | D02176 | | 13 | | | | | D05644J | | 8 | | ALL |
| 042 | 22 | | PA | 4-0 | 21-58-15 | D02176 | | 15 | | | | | GD0004 | D.. | 2 | | ALL |
| 043 | 22 | | PA | 4-0 | 21-58-15 | D02176 | | 12 | | | | | TB0182X | C016 | BJ | | ALL |
| 044 | 24 | | PK | 3-0 | 21-58-15 | D02176 | | 33 | | | | | D05644J | | 4 | | ALL |
| 045 | 24 | | PK | 3-0 | 21-58-15 | D02176 | | 11 | | | | | D05644J | | 7 | | ALL |
| 046 | 24 | | PK | 3-0 | 21-58-15 | D02176 | | 32 | | | | | D05644J | | 1 | | ALL |
| 047 | 22 | | PA | 3-0 | 36-11-52 | D05644J | | 14 | | | | | TB0248X | B012 | BJ | | ALL |
| 048 | 24 | | PK | 3-0 | 21-58-15 | D02176 | | 37 | | | | | TB0248X | A012 | BJ | | ALL |
| 050 | 24 | | PK | 3-0 | 21-26-11 | D01874 | | 7 | | | | | D05644J | | 21 | | ALL |
| 051 | 22 | | PA | 4-0 | 21-26-11 | D01874 | | 9 | | | | | GD0002 | D.. | 2 | | ALL |
| 052 | 24 | | PK | 3-0 | 21-26-11 | D01874 | | 28 | | | | | D05644J | | 22 | | ALL |
| 053 | 24 | | PK | 3-0 | 21-26-11 | D01874 | | 8 | | | | | D05644J | | 18 | | ALL |
| 054 | 24 | | PK | 3-0 | 21-26-11 | D01874 | | 6 | | | | | D05644J | | 20 | | ALL |
| 055 | 24 | | PK | 3-0 | 21-26-11 | D01874 | | 27 | | | | | D05644J | | 17 | | ALL |
| 056 | 24 | | PK | 3-0 | 21-26-11 | D01874 | | 36 | | | | | D05644J | | 32 | | ALL |
| 063 | 24 | | PK | 4-0 | 21-58-15 | D02176 | | 14 | | | | | TB0158F | C020 | 2 | | ALL |
| 064 | 24 | | PK | 3-0 | 73-21-18 | D05552J | | 1 | | | | | TB0182Y | C008 | BJ | | ALL |
| 065 | 24 | | PK | 3-0 | 73-21-18 | D05552J | | 2 | | | | | TB0182X | A012 | BJ | | ALL |
| 066 | 24 | | PK | 4-0 | 21-26-11 | D01874 | | 35 | | | | | TB0248X | C011 | BJ | | ALL |
| 067 | 24 | | PK | 4-0 | 21-58-15 | TB0158F | | C017 | | 2 | | | D02176 | | 38 | | ALL |
| 068 | 24 | | PK | 4-0 | 21-53-12 | D01870 | | 19 | | | | | D05552J | | 45 | | ALL |
| 069 | 22 | | PA | 5-0 | 21-53-12 | D01870 | | 21 | | | | | GD0002 | D.. | 2 | | ALL |
| 070 | 24 | | PK | 4-0 | 21-53-12 | D01870 | | 6 | | | | | D05552J | | 40 | | ALL |
| 071 | 24 | | PK | 4-0 | 21-53-12 | D01870 | | 3 | | | | | TB0182X | B012 | BJ | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1080 | 286T1080 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 072 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 37 | | | | D05552J | 42 | | | ALL |
| 073 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 36 | | | | D05552J | 43 | | | ALL |
| 074 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 35 | | | | D05552J | 44 | | | ALL |
| 075 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 8 | | | | TB0158F | A012 | 2 | | ALL |
| 076 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 4 | | | | D05552J | 50 | | | ALL |
| 077 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 10 | | | | D05552J | 51 | | | ALL |
| 078 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 7 | | | | D05552J | 48 | | | ALL |
| 079 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 11 | | | | D05552J | 49 | | | ALL |
| 080 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 12 | | | | D05552J | 46 | | | ALL |
| 081 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 9 | | | | D05552J | 47 | | | ALL |
| 082 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 16 | | | | D05552J | 34 | | | ALL |
| 083 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 14 | | | | D05552J | 35 | | | ALL |
| 084 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 15 | | | | D05552J | 36 | | | ALL |
| 085 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 13 | | | | D05552J | 37 | | | ALL |
| 086 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 18 | | | | D05552J | 38 | | | ALL |
| 087 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 17 | | | | D05552J | 39 | | | ALL |
| 088 | 24 | | PK | | 4-0 | 21-53-12 | D01870 | | 5 | | | | D05552J | 33 | | | ALL |
| 089 | 24 | | PV | CA | 3-0 | 21-58-11 | D01872 | | 19 | | | | TB0158F | C011 | 2 | | ALL |
| 089Z | | | | CA | 0-0 | 21-58-11 | D01872 | DED | | | | | TB0158F | DED | | | ALL |
| 090 | 22 | | PA | | 4-0 | 21-58-11 | D01872 | | 41 | | | | GD0002 | D.. | 2 | | ALL |
| 091 | 24 | | PK | | 3-0 | 21-58-11 | D01872 | | 3 | | | | TB0182Y | C002 | BJ | | ALL |
| 092 | 24 | | PK | | 3-0 | 21-58-11 | D01872 | | 4 | | | | TB0158Y | C003 | BJ | | 050-099, 277-299 |
| 092 | 24 | | PK | | 3-0 | 21-58-11 | D01872 | | 4 | | | | TB0158G | 2 | 2 | | 150-199, 275-276 |
| 093 | 24 | | PK | | 3-0 | 21-58-11 | D01872 | | 5 | | | | TB0182Y | A001 | BJ | | ALL |
| 094 | 24 | | PK | | 3-0 | 21-58-11 | D01872 | | 6 | | | | TB0248X | A001 | BJ | | ALL |
| 096 | 24 | | PK | | 4-0 | 21-58-12 | D01872 | | 7 | | | | TB0182X | B028 | BJ | | ALL |
| 098 | 24 | | PK | | 4-0 | 21-58-12 | D01872 | | 10 | | | | TB0182X | A028 | BJ | | ALL |
| 099 | 24 | | PK | | 4-0 | 21-58-12 | D01872 | | 9 | | | | TB0182X | C028 | BJ | | ALL |
| 101 | 22 | | PA | | 3-0 | 21-58-11 | D01872 | | 15 | | | | TB0182X | B011 | BJ | | ALL |
| 102 | 24 | | PK | | 3-0 | 33-16-11 | D01872 | | 12 | | | | D05552J | 61 | | | ALL |
| 103 | 24 | | PK | | 3-0 | 21-58-11 | D05644J | | 41 | | | | D01872 | 20 | | | ALL |
| 104R | 22 | | PH | | 3-0 | 26-18-22 | D05766J | | 19 | | | | D01876 | 36 | | | ALL |
| 105 | 22 | | PA | | 4-0 | 21-58-11 | D01872 | | 21 | | | | GD0002 | D.. | 2 | | ALL |
| 106R | 22 | | PH | | 3-0 | 26-18-22 | D05766J | | 20 | | | | D01876 | 57 | | | ALL |
| 107 | 24 | | PK | | 3-0 | 21-58-11 | D01872 | | 14 | | | | D05644J | 28 | | | ALL |
| 108R | 22 | | PH | | 3-0 | 26-18-22 | SP03260 | | | S | | | D01876 | 6 | | | 050-099, 275-299 |
| 108R | 22 | | PH | | 3-0 | 26-18-22 | D01876 | | 6 | | | | TB0248X | C001 | BJ | | 150-199 |
| 109 | 22 | | PA | | 3-0 | 21-58-11 | D01872 | | 17 | | | | TB0158F | A011 | 2 | | ALL |
| 111 | 22 | | PA | | 3-0 | 21-58-11 | TB0182Y | A002 | BJ | | | | D05644J | 24 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1080
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|----|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1080 | 286T1080 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | | | |
| 114 | 22 | | PA | | 3-0 | 36-11-52 | D01876 | | 60 | | | | | | SM00002 | | W | | ALL |
| 116 | 22 | | PA | | 3-0 | 36-11-52 | D01876 | | 40 | | | | | | D05766J | 14 | | | ALL |
| 119 | 24 | | PK | | 3-0 | 36-11-52 | D01876 | | 55 | | | | | | SM00001 | | W | | ALL |
| 120 | 24 | | PK | | 4-0 | 36-11-52 | D01876 | | 5 | | | | | | TB0248X | A011 | BJ | | ALL |
| 121 | 24 | | PK | | 3-0 | 36-11-52 | D01876 | | 20 | | | | | | D05644J | 35 | | | ALL |
| 122 | 22 | | PA | | 3-0 | 36-11-52 | D01876 | | 35 | | | | | | D05644J | 36 | | | ALL |
| 123 | 24 | | PK | | 4-0 | 36-11-52 | D01876 | | 53 | | | | | | TB0158Y | A007 | BJ | | ALL |
| 124 | 24 | | PK | | 4-0 | 21-25-21 | D05552J | | 3 | | | | | | D01874 | 25 | | | ALL |
| 126 | 24 | | PK | | 3-0 | 36-11-52 | D01876 | | 52 | | | | | | D05644J | 37 | | | ALL |
| 128 | 24 | | PK | | 4-0 | 36-11-62 | D01876 | | 37 | | | | | | TB0248X | B011 | BJ | | ALL |
| 129 | 22 | | PA | | 3-0 | 36-22-11 | D01876 | | 2 | | | | | | D05644J | 38 | | | ALL |
| 130 | 24 | | PK | | 3-0 | 36-11-62 | D01876 | | 1 | | | | | | D05766J | 7 | | | ALL |
| 131 | 22 | | PA | | 3-0 | 36-11-62 | D01876 | | 56 | | | | | | D05766J | 10 | | | ALL |
| 132 | 22 | | PA | | 3-0 | 36-22-11 | D05644J | | 29 | | | | | | TB0248Y | C009 | BJ | | ALL |
| 135 | 22 | | PA | | 3-0 | 36-11-62 | D01876 | | 31 | | | | | | D05766J | 8 | | | ALL |
| 136 | 24 | | PK | | 3-0 | 36-11-62 | D01876 | | 58 | | | | | | D05766J | 9 | | | ALL |
| 137 | 24 | | PK | | 3-0 | 36-11-62 | D01876 | | 28 | | | | | | D05766J | 11 | | | ALL |
| 138 | 24 | | PV | FM | 3-0 | 73-21-12 | D02162 | | 40 | | | | | | D05552J | 56 | | | ALL |
| 138F | 20 | | UA | | 3-0 | 73-21-12 | D02162 | | | | | FM | | | GDY0002 | S.. | 2 | | 050-099, 150-199 |
| 138F | 20 | | UA | | 4-0 | 73-21-12 | D02162 | | | | | FA | | | GDY0002 | S.. | 2 | | 275-276 |
| 138Z | | | | FM | 0-0 | 73-21-12 | D02162 | | | | | FM | | | D05552J | | | GI | 050-099, 150-199 |
| 138Z | | | | FM | 0-0 | 73-21-12 | D02162 | | | | | FA | | | D05552J | 57 | | | 275-276 |
| 138Z | | | | FM | 0-0 | 73-21-12 | D02162 | | | | | FD | | | D05552J | 57 | | | 277-299 |
| 139 | 24 | | PK | | 3-0 | 36-11-52 | TB0158Y | | | A007 | BJ | | | | D05766J | 1 | | | ALL |
| 140 | 24 | | PK | | 3-0 | 36-11-52 | TB0158Y | | | A007 | BJ | | | | D05766J | 4 | | | ALL |
| 141 | 22 | | PA | | 2-0 | 36-11-62 | SM00007 | | | | W | | | | D05766J | 6 | | | ALL |
| 143 | 24 | | PK | | 3-0 | 21-51-21 | TB0158Y | | | C004 | BJ | | | | D05552J | 9 | | | 050-099, 277-299 |
| 143 | 24 | | PK | | 3-0 | 21-51-21 | TB0158G | | | 4 | 2 | | | | D05552J | 9 | | | 150-199, 275-276 |
| 144 | 24 | | PK | | 3-0 | 36-11-62 | D05766J | | | 21 | | | | | D01876 | 47 | | | 050-099, 150-199 |
| 144 | 24 | | PK | | 3-0 | 36-11-62 | D01876 | | | 47 | | | | | D05766J | 21 | | | 275-299 |
| 145 | 24 | | PK | | 3-0 | 36-11-62 | D05766J | | | 22 | | | | | D01876 | 18 | | | 050-099, 150-199 |
| 145 | 24 | | PK | | 3-0 | 36-11-62 | D01876 | | | 18 | | | | | D05766J | 22 | | | 275-299 |
| 147 | 24 | | PK | | 3-0 | 22-12-21 | D02676 | | | 22 | | | | | D04887J | 6 | | | ALL |
| 148 | 24 | | PK | | 3-0 | 22-12-21 | D02676 | | | 23 | | | | | D04887J | 7 | | | ALL |
| 150 | 22 | | PA | | 4-0 | 27-58-21 | D02676 | | | 8 | | | | | GDY0002 | A.. | 2 | | ALL |
| 152 | 24 | | PK | | 3-0 | 27-58-21 | D02676 | | | 7 | | | | | D08032J | 2 | | | ALL |
| 154 | 22 | | PA | | 3-0 | 36-11-62 | D05766J | | | 23 | | | | | D01876 | 27 | | | 050-099, 150-199 |
| 154 | 22 | | PA | | 3-0 | 36-11-62 | D01876 | | | 27 | | | | | D05766J | 23 | | | 275-299 |
| 155 | 24 | | PK | | 3-0 | 22-12-21 | D02676 | | | 38 | | | | | D04887J | 8 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1080 | 286T1080 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | | |
| 156 | 24 | | PK | | 3-0 | 22-12-21 | D02676 | | 39 | | | | D04887J | | 9 | | | ALL |
| 157 | 24 | | PK | | 4-0 | 73-21-15 | D02162 | | 66 | | | | TB0182Y | A003 | BJ | | | 050-099, 150-199 |
| 157 | 24 | | PK | | 3-0 | 73-21-15 | D02162 | | 66 | | | | TB0182Y | A003 | BJ | | | 275-299 |
| 158 | 24 | | PV | GH | 3-0 | 73-21-17 | D02162 | | 32 | | | | TB0182X | C012 | BJ | | | 050-099, 150-199 |
| 158 | 24 | | PV | BZ | 3-0 | 73-21-17 | D02162 | | 32 | | | | TB0182X | C012 | BJ | | | 275-299 |
| 158Z | | | | GH | 0-0 | 73-21-17 | D02162 | | DED | | | | TB0182X | DED | | | | 050-099, 150-199 |
| 158Z | | | | BZ | 0-0 | 73-21-17 | D02162 | | DED | | | | TB0182X | DED | | | | 275-299 |
| 159 | 24 | | PV | GI | 3-0 | 73-21-17 | TB0248Y | | C003 | BJ | | | D05552J | | 32 | | | ALL |
| 159F | 20 | | UA | | 2-0 | 73-21-17 | GDX0002 | | S.. | 2 | | | D05552J | | | | GI | 050-099, 150-199 |
| 159F | 20 | | UA | | 3-0 | 73-21-17 | D05552J | | | | GI | | GDX0002 | | S.. | 2 | | 275-299 |
| 159Z | | | | GI | 0-0 | 73-21-17 | TB0248Y | | A004 | BJ | | | D05552J | | | | GI | 050-099, 150-199 |
| 159Z | | | | GI | 0-0 | 73-21-17 | D05552J | | | | GI | | TB0248Y | | | | FK | 275-276 |
| 159Z | | | | GI | 0-0 | 73-21-17 | D05552J | | | | GI | | TB0248Y | A004 | BJ | | | 277-299 |
| 160 | 24 | | PK | | 3-0 | 73-21-19 | D08032J | | 33 | | | | TB0248D | A021 | 2 | | | 050-099, 150-199 |
| 160 | 24 | | PK | | 3-0 | 73-21-19 | TB0248D | | A021 | 2 | | | D08032J | | 33 | | | 275-299 |
| 161 | 24 | | PK | | 3-0 | 73-21-19 | D02162 | | 19 | | | | TB0248D | C021 | 2 | | | 050-099, 150-199 |
| 161 | 24 | | PK | | 4-0 | 73-21-19 | D02162 | | 19 | | | | TB0248D | C021 | 2 | | | 275-299 |
| 162 | 22 | | PA | | 3-0 | 73-21-19 | D02162 | | 2 | | | | D08032J | | 19 | | | ALL |
| 163 | 24 | | PK | | 3-0 | 73-21-19 | D02162 | | 35 | | | | D08032J | | 32 | | | 050-099, 150-199 |
| 163 | 22 | | PA | | 3-0 | 73-21-19 | D02162 | | 35 | | | | D08032J | | 32 | | | 275-299 |
| 164 | 20 | | UA | | 3-0 | 73-21-17 | D02162 | | | | FE | | GDX0002 | | S.. | 2 | | 050-099, 150-199 |
| 164 | 20 | | UA | | 4-0 | 73-21-17 | D02162 | | | | FA | | GDX0002 | | S.. | 2 | | 275-276 |
| 164 | 20 | | UA | | 4-0 | 73-21-17 | D02162 | | | | FE | | GDX0002 | | S.. | 2 | | 277-299 |
| 167 | 24 | | PK | | 3-0 | 22-32-13 | D04887J | | 15 | | | | D02162 | | 62 | | | 050-099, 150-199 |
| 167 | 24 | | PK | | 3-0 | 22-32-13 | D02162 | | 62 | | | | D04887J | | 15 | | | 275-299 |
| 168 | 24 | | PV | GR | 4-0 | 73-21-17 | D02162 | | 6 | | | | TB0248Z | | 5 | BJ | | 050-099, 150-199, 277-278 |
| 168 | 24 | | PV | G | 4-0 | 73-21-17 | D02162 | | 6 | | | | TB0248Z | | 5 | BJ | | 275-276, 280-299 |
| 168Z | | | | GR | 0-0 | 73-21-17 | D02162 | | | | FE | | TB0248Z | | 6 | BJ | | 050-099, 150-199, 277-278 |
| 168Z | | | | G | 0-0 | 73-21-17 | D02162 | | | | FA | | TB0248Z | | 6 | BJ | | 275-276 |
| 168Z | | | | G | 0-0 | 73-21-17 | D02162 | | | | FE | | TB0248Z | | 6 | BJ | | 280-299 |
| 169 | 24 | | PV | GS | 3-0 | 73-21-12 | D02162 | | 8 | | | | D08032J | | 16 | | | 050-099, 150-199, 277-299 |
| 169 | 24 | | PV | H | 3-0 | 73-21-12 | D02162 | | 8 | | | | D08032J | | 16 | | | 275-276 |
| 169Z | | | | GS | 0-0 | 73-21-12 | D02162 | | | | FE | | D08032J | | | | FF | 050-099, 150-199, 277-299 |
| 169Z | | | | H | 0-0 | 73-21-12 | D02162 | | | | FA | | D08032J | | | | FF | 275-276 |
| 170 | 24 | | PK | | 3-0 | 73-21-12 | D02162 | | 7 | | | | D08032J | | 29 | | | ALL |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|---|----|-----|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1080 | 286T1080 | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | | | |
| 172 | 22 | PQ | GV | 3-0 | 73-21-11 | D08032J | | 5 | | | | | TB0182X | A027 | BJ | | 050-099, 150-199 |
| 172 | 22 | PQ | GV | 3-0 | 73-21-11 | TB0182X | | A027 | BJ | | | | D08032J | 5 | | | 275-278 |
| 172 | 24 | PV | GV | 3-0 | 73-21-11 | TB0182X | | A027 | BJ | | | | D08032J | 5 | | | 280-299 |
| 172Z | | | GV | 0-0 | 73-21-11 | D08032J | | | | | M4 | | TB0182X | B027 | BJ | | ALL |
| 173 | 24 | PK | | 4-0 | 73-21-17 | TB0182Y | | C003 | BJ | | | | D02162 | 61 | | | 050-099, 150-199 |
| 173 | 24 | PK | | 3-0 | 73-21-17 | D02162 | | 61 | | | | | TB0182Y | C003 | BJ | | 275-299 |
| 174 | 24 | PK | | 3-0 | 22-32-13 | D04887J | | 14 | | | | | D02162 | 53 | | | 050-099, 150-199 |
| 174 | 24 | PK | | 3-0 | 22-32-13 | D02162 | | 53 | | | | | D04887J | 14 | | | 275-299 |
| 176 | 24 | PK | | 3-0 | 22-32-13 | D04887J | | 18 | | | | | D02162 | 30 | | | 050-099, 150-199 |
| 176 | 24 | PK | | 3-0 | 22-32-13 | D02162 | | 30 | | | | | D04887J | 18 | | | 275-299 |
| 177 | 22 | PQ | HB | 2-0 | 73-21-19 | D08032J | | 43 | | | | | TB0248Y | C003 | BJ | | 050-099, 150-199 |
| 177 | 22 | PQ | HB | 3-0 | 73-21-19 | TB0248Y | | C003 | BJ | | | | D08032J | 43 | | | 275-299 |
| 177Z | | | HB | 0-0 | 73-21-19 | D08032J | | 44 | | | | | TB0248Y | A004 | BJ | | 050-099, 150-199 |
| 177Z | | | HB | 0-0 | 73-21-19 | TB0248Y | | A004 | BJ | | | | D08032J | 44 | | | 275-299 |
| 178 | 24 | PK | | 3-0 | 73-21-16 | D02162 | | 64 | | | | | D08032J | 35 | | | ALL |
| 181 | 24 | PK | | 3-0 | 73-21-18 | D08032J | | 6 | | | | | TB0248X | B016 | BJ | | ALL |
| 182 | 24 | PK | | 3-0 | 73-21-17 | D08032J | | 3 | | | | | TB0182Y | C003 | BJ | | 050-099, 150-199 |
| 182 | 24 | PK | | 3-0 | 73-21-17 | TB0182Y | | C003 | BJ | | | | D08032J | 3 | | | 275-299 |
| 183 | 24 | PK | | 3-0 | 73-21-15 | TB0182Y | | C005 | BJ | | | | D08032J | 17 | | | ALL |
| 184 | 24 | PK | | 3-0 | 22-32-13 | TB0182Y | | A006 | BJ | | | | D04887J | 11 | | | ALL |
| 185 | 24 | PK | | 3-0 | 22-32-13 | TB0182Y | | A003 | BJ | | | | D04887J | 12 | | | ALL |
| 186 | 24 | PV | HK | 3-0 | 73-21-17 | TB0248Z | | 5 | BJ | | | | D08032J | 7 | | | ALL |
| 186Z | | | HK | 0-0 | 73-21-17 | TB0248Z | | 6 | BJ | | | | D08032J | | | FF | ALL |
| 191 | 24 | PK | | 4-0 | 73-21-17 | D02162 | | 42 | | | | | TB0182Y | C003 | BJ | | 050-099, 150-199 |
| 191 | 24 | PK | | 3-0 | 73-21-17 | D02162 | | 42 | | | | | TB0182Y | C003 | BJ | | 275-299 |
| 192 | 22 | PA | | 3-0 | 36-11-62 | D05766J | | 24 | | | | | D01876 | 61 | | | 050-099, 150-199 |
| 192 | 22 | PA | | 3-0 | 36-11-62 | D01876 | | 61 | | | | | D05766J | 24 | | | 275-299 |
| 195 | 24 | PK | | 3-0 | 22-32-13 | D04887J | | 17 | | | | | D02162 | 23 | | | 050-099, 150-199 |
| 195 | 24 | PK | | 3-0 | 22-32-13 | D02162 | | 23 | | | | | D04887J | 17 | | | 275-299 |
| 196 | 24 | PK | | 4-0 | 73-21-15 | D02162 | | 59 | | | | | TB0182Y | C005 | BJ | | 050-099, 150-199 |
| 196 | 24 | PK | | 3-0 | 73-21-15 | D02162 | | 59 | | | | | TB0182Y | C005 | BJ | | 275-299 |
| 197 | 24 | PK | | 3-0 | 22-32-13 | D04887J | | 16 | | | | | D02162 | 26 | | | 050-099, 150-199 |
| 197 | 24 | PK | | 3-0 | 22-32-13 | D02162 | | 26 | | | | | D04887J | 16 | | | 275-299 |
| 198 | 24 | PK | | 4-0 | 73-21-15 | D02162 | | 65 | | | | | TB0182Y | A006 | BJ | | 050-099, 150-199 |
| 198 | 24 | PK | | 3-0 | 73-21-15 | D02162 | | 65 | | | | | TB0182Y | A006 | BJ | | 275-299 |
| 200 | 24 | PK | | 3-0 | 36-11-62 | TB0248X | | D011 | BJ | | | | D01876 | 65 | | | 050-099, 150-199 |
| 200 | 24 | PK | | 4-0 | 36-11-62 | D01876 | | 65 | | | | | TB0248X | D011 | BJ | | 275-299 |
| 201B | 24 | PL | A | 3-0 | 27-51-11 | D02676 | | 17 | | | | | D08032J | 25 | | | ALL |
| 201R | 24 | PL | A | 0-0 | 27-51-11 | D02676 | | 18 | | | | | D08032J | 26 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|--------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1080 | 286T1080 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | |
| 202B | 24 | PL | B | 3-0 | 27-58-21 | D02676 | | 9 | | D08032J | | 20 | | | ALL |
| 202R | 24 | PL | B | 0-0 | 27-58-21 | D02676 | | 10 | | D08032J | | 21 | | | ALL |
| 203B | 22 | PB | P | 3-0 | 27-41-21 | D02676 | | 41 | | D04887J | | 5 | | | ALL |
| 203R | 22 | PB | P | 0-0 | 27-41-21 | D02676 | | 40 | | D04887J | | 4 | | | ALL |
| 206B | 24 | PL | AA | 3-0 | 27-58-21 | D02676 | | 35 | | D04887J | | 30 | | | ALL |
| 206R | 24 | PL | AA | 0-0 | 27-58-21 | D02676 | | 31 | | D04887J | | 31 | | | ALL |
| 207B | 24 | PL | AD | 3-0 | 27-32-21 | D02676 | | 21 | | D04887J | | 29 | | | ALL |
| 207R | 24 | PL | AD | 0-0 | 27-32-21 | D02676 | | 19 | | D04887J | | 28 | | | ALL |
| 211B | 24 | PW | IK | 3-0 | 77-12-12 | D08032J | | 50 | | TB0182Y | C013 | BJ | | | 050-099, 162-199, 277-299 |
| 211B | 24 | PW | IK | 3-0 | 77-12-12 | D08032J | | 50 | | TB0158Y | C025 | BJ | | | 150-157, 275-276 |
| 211R | 24 | PW | IK | 0-0 | 77-12-12 | D08032J | | 47 | | TB0182Y | A013 | BJ | | | 050-099, 162-199, 277-299 |
| 211R | 24 | PW | IK | 0-0 | 77-12-12 | D08032J | | 47 | | TB0158Y | A025 | BJ | | | 150-157, 275-276 |
| 211Z | | | IK | 0-0 | 77-12-12 | D08032J | | 49 | | TB0182Y | REF | | FG | | 050-099, 162-199, 277-299 |
| 211Z | | | IK | 0-0 | 77-12-12 | D08032J | | 49 | | TB0158Z | 27 | BJ | | | 150-157, 275-276 |
| 217 | 24 | PK | | 3-0 | 36-11-62 | D05766J | | 31 | | D01876 | 17 | | | | 050-099, 150-199 |
| 217 | 24 | PK | | 3-0 | 36-11-62 | D01876 | | 17 | | D05766J | 31 | | | | 275-299 |
| 218B | 24 | PW | IO | 3-0 | 77-12-12 | D08032J | | 14 | | TB0182Y | C013 | BJ | | | 050-099, 162-199 |
| 218B | 24 | PW | IO | 3-0 | 77-12-12 | D08032J | | 14 | | TB0158Y | C025 | BJ | | | 150-157 |
| 218B | 24 | PW | IR | 3-0 | 77-12-12 | D08032J | | 14 | | TB0158Y | C025 | BJ | | | 275-276 |
| 218B | 24 | PW | IR | 3-0 | 77-12-12 | D08032J | | 14 | | TB0182Y | C013 | BJ | | | 277-299 |
| 218R | 24 | PW | IO | 0-0 | 77-12-12 | D08032J | | 13 | | TB0182Y | A013 | BJ | | | 050-099, 162-199 |
| 218R | 24 | PW | IO | 0-0 | 77-12-12 | D08032J | | 13 | | TB0158Y | A025 | BJ | | | 150-157 |
| 218R | 24 | PW | IR | 0-0 | 77-12-12 | D08032J | | 13 | | TB0158Y | A025 | BJ | | | 275-276 |
| 218R | 24 | PW | IR | 0-0 | 77-12-12 | D08032J | | 13 | | TB0182Y | A013 | BJ | | | 277-299 |
| 218Z | | | IO | 0-0 | 77-12-12 | D08032J | | 15 | | TB0182Y | REF | | FG | | 050-099, 162-199 |
| 218Z | | | IO | 0-0 | 77-12-12 | D08032J | | 15 | | TB0158Z | 27 | BJ | | | 150-157 |
| 218Z | | | IR | 0-0 | 77-12-12 | D08032J | | 15 | | TB0158Z | 27 | BJ | | | 275-276 |
| 218Z | | | IR | 0-0 | 77-12-12 | D08032J | | 15 | | TB0182Y | REF | | FG | | 277-299 |
| 248 | 22 | PA | | 3-0 | 36-11-62 | D01876 | | 66 | | SM00007 | | W | | | ALL |
| 249 | 22 | PA | | 3-0 | 36-11-62 | D01876 | | 34 | | SM00007 | | W | | | ALL |
| 301B | 24 | PM | C | 3-0 | 27-58-21 | D02676 | | 12 | | D08032J | | 22 | | | ALL |
| 301R | 24 | PM | C | 0-0 | 27-58-21 | D02676 | | 13 | | D08032J | | 23 | | | ALL |
| 301Y | 24 | PM | C | 0-0 | 27-58-21 | D02676 | | 11 | | D08032J | | 24 | | | ALL |
| 304B | 24 | PM | AB | 3-0 | 27-58-21 | D02676 | | 32 | | D04887J | | 32 | | | ALL |
| 304R | 24 | PM | AB | 0-0 | 27-58-21 | D02676 | | 33 | | D04887J | | 33 | | | ALL |
| 304Y | 24 | PM | AB | 0-0 | 27-58-21 | D02676 | | 34 | | D04887J | | 34 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1080
Page 7
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|---------|-------------|-----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1080 | 286T1080 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 438 | 24 | PV | RM | 3-0 | 73-21-12 | D02162 | | 41 | | | | | TB0248Z | 5 | BJ | | 050-099, 150-199 |
| 438 | 24 | PV | RM | 4-0 | 73-21-12 | D02162 | | 41 | | | | | TB0248Z | 5 | BJ | | 275-299 |
| 438F | 20 | UA | | 3-0 | 73-21-12 | D02162 | | | | | | | FD | GD0002 | S.. | 2 | 050-099, 150-199 |
| 438F | 20 | UA | | 4-0 | 73-21-12 | D02162 | | | | | | | FD | GD0002 | S.. | 2 | 277-299 |
| 438Z | | | RM | 0-0 | 73-21-12 | D02162 | | | | | | | FD | TB0248Z | | 6 | 050-099, 150-199, 277-299 |
| 438Z | | | RM | 0-0 | 73-21-12 | D02162 | | | | | | | FA | TB0248Z | | 6 | 275-276 |
| 500 | 24 | PK | | 3-0 | 21-58-11 | D05644J | | 40 | | | | | | D01872 | | 1 | ALL |
| 502 | 24 | PK | | 3-0 | 34-61-13 | D02162 | | 57 | | | | | | TB0158Y | A003 | BJ | 050-099, 277-299 |
| 502 | 24 | PK | | 4-0 | 34-61-13 | D02162 | | 57 | | | | | | TB0158G | | 2 | 150-199 |
| 502 | 24 | PK | | 3-0 | 34-61-13 | D02162 | | 57 | | | | | | TB0158G | | 2 | 275-276 |
| 503 | 24 | PK | | 4-0 | 34-61-13 | D02162 | | 55 | | | | | | TB0158G | | 2 | ALL |
| 504 | 24 | PK | | 4-0 | 34-61-13 | D02162 | | 1 | | | | | | TB0158G | | 2 | ALL |
| 505 | 24 | PK | | 4-0 | 34-61-13 | D02162 | | 21 | | | | | | TB0158G | | 2 | ALL |
| 506 | 24 | PK | | 4-0 | 34-61-13 | D02162 | | 29 | | | | | | TB0158G | | 2 | ALL |
| 507 | 24 | PK | | 3-0 | 34-61-23 | TB0158Y | | | A003 | BJ | | | | D04809J | | 1 | 050-099, 277-299 |
| 507 | 24 | PK | | 3-0 | 34-61-23 | TB0158G | | 1 | | | | | | D04809J | | 1 | 150-199, 275-276 |
| 508 | 24 | PK | | 3-0 | 34-61-23 | TB0158G | | 18 | | 2 | | | | D04809J | | 2 | ALL |
| 509 | 24 | PK | | 3-0 | 34-61-23 | TB0158G | | 21 | | 2 | | | | D04809J | | 3 | ALL |
| 510 | 24 | PK | | 3-0 | 34-61-23 | TB0158G | | 22 | | 2 | | | | D04809J | | 4 | ALL |
| 511 | 24 | PK | | 3-0 | 34-61-23 | TB0158G | | 23 | | 2 | | | | D04809J | | 5 | ALL |
| 512 | 24 | PV | R | 3-0 | 34-61-23 | TB0182Y | | | A005 | BJ | | | | D04809J | | 6 | ALL |
| 512Z | | | R | 0-0 | 34-61-23 | D04809J | | | DED | | | | | TB0182Y | | DED | ALL |
| 513 | 24 | PV | S | 3-0 | 34-61-23 | TB0182Y | | | A004 | BJ | | | | D04809J | | 7 | ALL |
| 513Z | | | S | 0-0 | 34-61-23 | D04809J | | | DED | | | | | TB0182Y | | DED | ALL |
| 514 | 24 | PV | T | 3-0 | 34-61-23 | TB0182Y | | | A009 | BJ | | | | D04809J | | 8 | ALL |
| 514Z | | | T | 0-0 | 34-61-23 | D04809J | | | DED | | | | | TB0182Y | | DED | ALL |
| 515 | 24 | PV | U | 3-0 | 34-61-23 | TB0182Y | | | C009 | BJ | | | | D04809J | | 9 | ALL |
| 515Z | | | U | 0-0 | 34-61-23 | D04809J | | | DED | | | | | TB0182Y | | DED | ALL |
| 516 | 24 | PV | V | 3-0 | 34-61-23 | TB0182Y | | | A010 | BJ | | | | D04809J | | 10 | ALL |
| 516Z | | | V | 0-0 | 34-61-23 | D04809J | | | DED | | | | | TB0182Y | | DED | ALL |
| 518 | 22 | PA | | 4-0 | 27-58-21 | D02676 | | 43 | | | | | | GD0002 | | 2 | ALL |
| 521 | 22 | PA | | 4-0 | 27-61-11 | D02676 | | 29 | | | | | | TB0158D | | 2 | 050-099 |
| 521 | 22 | PA | | 3-0 | 27-61-11 | D02676 | | 29 | | | | | | TB0182D | | 2 | 150-152 |
| 521 | 22 | PA | | 3-0 | 27-61-11 | D02676 | | 29 | | | | | | TB0158D | | 2 | 153-156, 162-166 |
| 521 | 22 | PA | | 4-0 | 27-61-11 | D02676 | | 29 | | | | | | D04887J | | 27 | 157, 167-199, 277-299 |
| 521 | 22 | PA | | 3-0 | 27-61-11 | D02676 | | 29 | | | | | | D04887J | | 27 | 275-276 |
| 522 | 22 | PA | | 3-0 | 27-61-11 | D04887J | | 27 | | | | | | TB0158D | | 2 | 153-154 |
| 523 | 22 | PA | | 3-0 | 22-24-21 | D02676 | | 26 | | | | | | D04887J | | 1 | ALL |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1080 | 286T1080 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | |
| 524 | 24 | | PK | | 4-0 | 21-51-11 | TB0182X | A016 | BJ | | D01876 | 4 | | | ALL |
| 525 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 3 | | | TB0158G | 9 | 2 | | ALL |
| 526 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 16 | | | TB0182X | B016 | BJ | | ALL |
| 527 | 24 | | PK | | 3-0 | 21-51-21 | D01868 | 37 | | | D01876 | 38 | | | ALL |
| 528 | 24 | | PK | | 4-0 | 21-51-21 | D01868 | 38 | | | D08032J | 4 | | | ALL |
| 529 | 22 | | PA | | 2-0 | 27-61-11 | TB0158D | C013 | 2 | | TB0158D | C014 | 2 | | 153-154 |
| 530 | 24 | | PK | | 4-0 | 73-21-15 | D02162 | 33 | | | TB0158Y | A006 | BJ | | 050-099, 153-199, 280-299 |
| 530 | 24 | | PK | | 4-0 | 73-21-15 | D02162 | 33 | | | TB0158Y | A014 | BJ | | 150-152, 275-276 |
| 530 | 24 | | PK | | 3-0 | 73-21-15 | D02162 | 33 | | | TB0158Y | A006 | BJ | | 277-278 |
| 533 | 24 | | PK | | 3-0 | 73-21-17 | TB0182X | D012 | BJ | | D08032J | 31 | | | 050-099, 150-199 |
| 533 | 24 | | PK | | 2-4 | 73-21-17 | TB0182X | D012 | BJ | | D08032J | 31 | | | 275-299 |
| 534 | 24 | | PK | | 3-0 | 73-21-16 | D02162 | 54 | | | D05552J | 10 | | | 050-099, 150-199 |
| 534 | 24 | | PK | | 3-0 | 73-21-16 | D08032J | 30 | | | D02162 | 54 | | | 275-299 |
| 538 | 24 | | PK | | 4-0 | 21-53-22 | D01868 | 30 | | | TB0182X | C011 | BJ | | ALL |
| 540 | 24 | | PK | | 2-0 | 21-58-11 | D08032J | 37 | | | TB0182Y | C002 | BJ | | ALL |
| 542 | 24 | | PV | VQ | 3-0 | 73-21-11 | D05552J | 41 | | | TB0182Y | C006 | BJ | | ALL |
| 542Z | | | | VQ | 0-0 | 73-21-11 | TB0182Y | C004 | BJ | | D05552J | 59 | | | 050-099, 150-199 |
| 542Z | | | | VQ | 0-0 | 73-21-11 | D05552J | 59 | | | TB0182Y | C004 | BJ | | 275-299 |
| 543 | 24 | | PK | | 3-0 | 21-58-12 | D01872 | 11 | | | TB0182X | D028 | BJ | | ALL |
| 544JA | 24 | | PV | VS | 2-0 | 73-21-17 | TB0248Y | C003 | BJ | | TB0248Z | 5 | BJ | | 050-099, 150-199, 277-299 |
| 544JA | 24 | | PV | JA | 2-0 | 73-21-17 | TB0248Y | C003 | BJ | | TB0248Z | 5 | BJ | | 275-276 |
| 544Z | | | | VS | 0-0 | 73-21-17 | TB0248Y | A004 | BJ | | TB0248Z | 6 | BJ | | 050-099, 150-199, 277-299 |
| 544Z | | | | JA | 0-0 | 73-21-17 | TB0248Y | | | FK | TB0248Z | 6 | BJ | | 275-276 |
| 552 | 24 | | PV | BJ | 3-0 | 73-21-17 | D08032J | 55 | | | TB0248Z | 5 | BJ | | 050-099, 150-199 |
| 552 | 24 | | PV | AS | 3-0 | 73-21-17 | TB0248Z | 5 | BJ | | D08032J | 55 | | | 275-299 |
| 552Z | | | | BJ | 0-0 | 73-21-17 | D08032J | 56 | | | TB0248Z | 6 | BJ | | 050-099, 150-199 |
| 552Z | | | | AS | 0-0 | 73-21-17 | TB0248Z | 6 | BJ | | D08032J | 56 | | | 275-299 |
| 559 | 22 | | PA | | 3-0 | 27-61-11 | D04887J | 27 | | | TB0158D | A013 | 2 | | 050-099, 155-156, 162-166 |
| 559 | 22 | | PA | | 3-0 | 27-61-11 | D04887J | 27 | | | TB0182D | A022 | 2 | | 150-152 |
| 560 | 22 | | PA | | 3-0 | 27-61-11 | TB0158D | C013 | 2 | | TB0158D | C014 | 2 | | 050-099 |
| 560 | 22 | | PA | | 2-0 | 27-61-11 | TB0182D | C022 | 2 | | TB0182D | C024 | 2 | | 150-152 |
| 560 | 22 | | PA | | 2-0 | 27-61-11 | TB0158D | C013 | 2 | | TB0158D | C014 | 2 | | 155-156, 162-166 |
| 600 | 22 | | PA | | 3-0 | 27-41-21 | D02676 | 44 | | | D04887J | 26 | | | ALL |
| 601 | 24 | | PK | | 3-0 | 31-51-42 | D04809J | 23 | | | TB0182D | C026 | 2 | | 150-199, 275-299 |
| 609 | 24 | | PV | YI | 2-0 | 73-21-17 | D08032J | 11 | | | TB0248Z | 5 | BJ | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1080 | 286T1080 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 609 | 24 | PV | YI | 3-0 | 73-21-17 | D08032J | 11 | | | | | | TB0248Z | 5 | BJ | | 275-299 |
| 609Z | | | YI | 0-0 | 73-21-17 | D08032J | | | | | | | TB0248Z | 6 | BJ | | ALL |
| 614 | 24 | PK | | 3-0 | 73-21-18 | D05552J | 20 | | | | | | TB0248X | C016 | BJ | | 050-099, 150-199, 277-299 |
| 614 | 24 | PK | | 5-0 | 73-21-18 | D05552J | 20 | | | | | | TB0248X | C016 | BJ | | 275-276 |
| 685 | 24 | PV | D5 | 3-0 | 73-21-11 | D05766J | 25 | | | | | | TB0182Y | C006 | BJ | | ALL |
| 685Z | | | D5 | 0-0 | 73-21-11 | D05766J | 26 | | | | | | TB0182Y | C004 | BJ | | ALL |
| 700 | 24 | PK | | 3-0 | 31-31-21 | D04809J | 17 | | | | | | D02676 | 14 | | | 050-099, 150-199 |
| 700 | 24 | PK | | 3-0 | 31-31-21 | D02676 | 14 | | | | | | D04809J | 17 | | | 275-299 |
| 701 | 22 | PA | | 3-0 | 21-51-21 | TB0182Y | C001 | BJ | | | | | D08032J | 54 | | | ALL |
| 703 | 24 | PK | | 3-0 | 31-31-21 | D04809J | 18 | | | | | | D02676 | 16 | | | ALL |
| 706 | 24 | PK | | 3-0 | 30-31-21 | D08032J | 51 | | | | | | TB0248Y | A014 | BJ | | ALL |
| 707 | 24 | PK | | 3-0 | 30-34-21 | TB0248X | D002 | BJ | | | | | D08032J | 52 | | | 050-099, 150-199 |
| 707 | 24 | PK | | 3-0 | 30-34-21 | D08032J | 52 | | | | | | TB0248X | D002 | BJ | | 275-299 |
| 708 | 24 | PK | | 4-0 | 21-51-13 | D01870 | 24 | | | | | | D05552J | 5 | | | ALL |
| 712 | 24 | PK | | 4-0 | 21-25-11 | D01874 | 2 | | | | | | TB0248D | A020 | 2 | | ALL |
| 713 | 24 | PK | | 3-0 | 21-25-11 | TB0248D | C020 | 2 | | | | | TB0248Y | C010 | BJ | | ALL |
| 714 | 22 | PA | | 3-0 | 73-21-19 | D08032J | 53 | | | | | | D02676 | 28 | | | ALL |
| 715 | 22 | PA | | 3-0 | 24-51-52 | D05766J | 15 | | | | | | TB0248X | A015 | BJ | | 050-099, 150-199 |
| 715 | 22 | PA | | 3-0 | 24-51-52 | D05766J | 15 | | | | | | TB0248Y | A009 | BJ | | 275-299 |
| 716 | 22 | PA | | 3-0 | 24-51-52 | D05766J | 16 | | | | | | TB0248X | B015 | BJ | | 050-099, 150-199 |
| 716 | 22 | PA | | 3-0 | 24-51-52 | D05766J | 16 | | | | | | TB0248Y | A010 | BJ | | 275-299 |
| 718 | 22 | PA | | 3-0 | 24-51-52 | D05766J | 17 | | | | | | TB0248X | C015 | BJ | | 050-099, 150-199 |
| 719 | 22 | PA | | 3-0 | 24-51-52 | D05766J | 18 | | | | | | TB0248X | D015 | BJ | | 050-099, 150-199 |
| 720 | 24 | PK | | 4-0 | 73-21-15 | TB0158G | 10 | 2 | | | | | D02162 | 24 | | | 050-099, 150-199 |
| 720 | 24 | PK | | 4-0 | 73-21-15 | D02162 | 24 | | | | | | TB0158G | 10 | 2 | | 275-299 |
| 722 | 22 | PA | | 3-0 | 21-24-11 | D02176 | 25 | | | | | | TB0182X | B015 | BJ | | 050-099, 150-199 |
| 723 | 24 | PK | | 3-0 | 21-24-11 | D02176 | 23 | | | | | | TB0182X | C015 | BJ | | 050-099, 150-199 |
| 724 | 24 | PK | | 3-0 | 21-24-11 | D02176 | 22 | | | | | | TB0182X | D015 | BJ | | 050-099, 150-199 |
| 725 | 22 | PA | | 4-0 | 21-24-11 | D02176 | 3 | | | | | | GDX0004 | D.. | 2 | | 050-099, 150-199 |
| 726 | 22 | PA | | 4-0 | 21-24-11 | D02176 | 4 | | | | | | GDX0004 | D.. | 2 | | 050-099, 150-199 |
| 728 | 24 | PK | | 3-0 | 21-24-11 | D02176 | 24 | | | | | | TB0182X | A015 | BJ | | 050-099, 150-199 |
| 729 | 24 | PK | | 3-0 | 21-24-11 | D02176 | 1 | | | | | | TB0248Y | A010 | BJ | | 050-099, 150-199 |
| 731 | 20 | PA | | 2-0 | 36-11-52 | D05766J | 27 | | | | | | SM00002 | | W | | 157, 167-199, 277-299 |
| 740 | 24 | PK | | 3-0 | 36-11-52 | D05644J | 25 | | | | | | SM00001 | | W | | ALL |
| 741 | 24 | PK | | 3-0 | 36-11-52 | D01876 | 54 | | | | | | SM00001 | | W | | ALL |
| 742 | 22 | PA | | 3-0 | 36-11-52 | D05644J | 34 | | | | | | SM00002 | | W | | ALL |
| 743 | 22 | PA | | 3-0 | 36-11-52 | D01876 | 59 | | | | | | SM00002 | | W | | ALL |
| 745 | 22 | PA | | 3-0 | 36-11-52 | D01876 | 11 | | | | | | D05766J | 3 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|-------|--------|-------|------|---------|--------|-------------|----|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1080 | 286T1080 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 746 | 22 | | PA | | 3-0 | 36-11-52 | D01876 | 46 | | | | | D05766J | 2 | | | ALL |
| 753 | 22 | | PA | | 4-0 | 36-22-11 | D01876 | 3 | | | | | TB0248Y | C009 | BJ | | ALL |
| 764 | 24 | | PV | M4 | 3-0 | 73-21-11 | D08032J | 48 | | | | | TB0248Z | 5 | BJ | | ALL |
| 764Z | | | | M4 | 0-0 | 73-21-11 | D08032J | | | | M4 | | TB0248Z | 6 | BJ | | ALL |
| 766 | 24 | | PK | | 4-0 | 21-51-21 | D02676 | 24 | | | | | TB0182D | C021 | 2 | | 050-099, 150-199, 275-276 |
| 768 | 24 | | PK | | 3-0 | 21-58-11 | D08032J | 40 | | | | | TB0158Y | C003 | BJ | | 050-099, 277-299 |
| 768 | 24 | | PK | | 2-0 | 21-58-11 | D08032J | 40 | | | | | TB0158G | 2 | 2 | | 150-199, 275-276 |
| 769 | 24 | | PK | | 3-0 | 27-51-11 | D02676 | 52 | | | | | D08032J | 36 | | | ALL |
| 775 | 24 | | PK | | 4-0 | 21-58-11 | D01872 | 8 | | | | | GDY0002 | D.. | 2 | | ALL |
| 776 | 24 | | PK | | 3-0 | 21-26-11 | D05644J | 33 | | | | | TB0158F | A020 | 2 | | ALL |
| 778 | 24 | | PK | | 2-0 | 73-21-15 | D05552J | 53 | | | | | TB0248X | C012 | BJ | | ALL |
| 780 | 24 | | PK | | 3-0 | 73-21-15 | D05552J | 55 | | | | | D02162 | 27 | | | ALL |
| 781 | 24 | | PK | | 3-0 | 73-21-19 | D08032J | 45 | | | | | TB0248D | C021 | 2 | | 050-099, 150-199 275-299 |
| 781 | 24 | | PK | | 3-0 | 73-21-19 | TB0248D | | C021 | 2 | | | D08032J | 45 | | | 050-099, 150-199 275-299 |
| FRA | | | | | 0-0 | 73-21-11 | D08032J | 39 | | | | | D08032J | | | M4 | 050-099, 150-199 |
| FRB | | | | | 0-0 | 73-21-17 | D08032J | 28 | | | | | D08032J | | | FF | 050-099, 150-199 |
| FRC | | | | | 0-0 | 73-21-12 | D05552J | | | | | GI | D05552J | 57 | | | 050-099, 150-199 |
| FRF | | | | | 0-0 | 73-21-17 | D08032J | | | | | FF | D08032J | 28 | | | 275-299 |
| FRG | | | | | 0-0 | 77-12-12 | TB0182Y | | REF | | | FG | TB0182Y | A014 | BJ | | 050-099, 162-199, 277-299 |
| FRK | | | | | 0-0 | 73-21-17 | TB0248Y | | | | | FK | TB0248Y | A004 | BJ | | 275-276 |
| FRM | | | | | 0-0 | 73-21-11 | D08032J | 39 | | | | | D08032J | | | M4 | 275-299 |
| PA1 | | | | | 0-0 | 99-99-99 | D01874 | 26 | | | | | D01874 | 34 | | | ALL |
| PB1 | | | | | 0-0 | 99-99-99 | D01868 | 25 | | | | | D01868 | 35 | | | ALL |
| PC1 | | | | | 0-0 | 99-99-99 | D01870 | 22 | | | | | D01870 | 38 | | | ALL |
| PD1 | | | | | 0-0 | 99-99-99 | D01872 | 24 | | | | | D01872 | 36 | | | ALL |
| PE1 | | | | | 0-0 | 21-58-15 | D02176 | 26 | | | | | D02176 | 34 | | | ALL |
| PF1 | | | | | 0-0 | 36-11-52 | D01876 | 41 | | | | | D01876 | 63 | | | 050-099, 150-156, 162-166, 275-276 |
| PF1 | | | | | 0-0 | 36-11-52 | D01876 | 9 | | | | | D01876 | 51 | | | 157, 167-199, 277-299 |
| PG1 | | | | | 0-0 | 73-21-15 | D02162 | 11 | | | | | D02162 | 20 | | | ALL |
| PH1 | | | | | 0-0 | 27-58-21 | D02676 | 47 | | | | | D02676 | 66 | | | 050-099, 150-154 |
| PH1 | | | | | 0-0 | 27-58-21 | D02676 | 47 | | | | | D02676 | 64 | | | 155-199, 275-299 |
| W1081 | 286T1081 | | | E2-6 SHELF, HF-R COAX | | | | | | | | | | | | | |
| 01CO | | | A | | 0-0 | 23-11-21 | D00643B | | = C71 | | | | D04005P | = C1 | | | ALL |
| 01CX | | 65 | A | | 4-0 | 23-11-21 | D00643B | | 71 | | | | D04005P | = A1 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1080
Page 11
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1082 | 286T1082 | | | FIRE DETECTION CARD FILE P54 | | | | | | | | | | | | | | |
| 001R | 22 | | PH | 4-0 | 26-11-11 | D07992J | | | | 1 | | | | TB0276Y | A005 | BJ | | ALL |
| 002 | 24 | | PK | 4-0 | 31-51-21 | D07992J | | | | 2 | | | | TB0276Y | A010 | BJ | | ALL |
| 003 | 24 | | PK | 4-0 | 31-51-21 | D07992J | | | | 3 | | | | TB0276Y | C017 | BJ | | ALL |
| 006R | 22 | | PH | 4-0 | 26-11-11 | D07992J | | | | 6 | | | | D02832 | 19 | | | ALL |
| 007R | 22 | | PH | 4-0 | 26-11-11 | D07992J | | | | 7 | | | | D02832 | 21 | | | ALL |
| 008R | 22 | | PH | 4-0 | 26-11-11 | D07992J | | | | 8 | | | | D02832 | 20 | | | ALL |
| 009R | 22 | | PH | 4-0 | 26-11-11 | D07992J | | | | 9 | | | | SM00009 | | W | | ALL |
| 011R | 22 | | PH | 4-0 | 26-11-12 | D07992J | | | | 11 | | | | TB0276Y | A006 | BJ | | ALL |
| 012R | 22 | | PH | 4-0 | 26-18-12 | D05540J | | | | 8 | | | | D04002J | 3 | | | 050-099, 275-299 |
| 012R | 22 | | PH | 3-0 | 26-18-12 | D05540J | | | | 8 | | | | D04002J | 3 | | | 150-199 |
| 016R | 22 | | PH | 4-0 | 26-11-12 | D07992J | | | | 16 | | | | D02834 | 21 | | | 050-099 |
| 016R | 22 | | PH | 3-0 | 26-11-12 | D07992J | | | | 16 | | | | D02834 | 21 | | | 150-199, 275-299 |
| 017R | 22 | | PH | 4-0 | 26-11-12 | D07992J | | | | 17 | | | | D02834 | 19 | | | 050-099 |
| 017R | 22 | | PH | 3-0 | 26-11-12 | D07992J | | | | 17 | | | | D02834 | 19 | | | 150-199, 275-299 |
| 018R | 22 | | PH | 4-0 | 26-11-12 | D07992J | | | | 18 | | | | D02834 | 20 | | | 050-099 |
| 018R | 22 | | PH | 3-0 | 26-11-12 | D07992J | | | | 18 | | | | D02834 | 20 | | | 150-199, 275-299 |
| 019R | 22 | | PH | 4-0 | 26-11-12 | D07992J | | | | 19 | | | | SM00019 | | W | | ALL |
| 051R | 22 | | PH | 3-0 | 26-11-11 | TB0276Y | | | A005 | BJ | | | | D02832 | 1 | | | ALL |
| 052R | 22 | | PH | 3-0 | 26-11-11 | TB0276Y | | | A005 | BJ | | | | D10092 | 2 | | | ALL |
| 053R | 22 | | PH | 0-3 | 26-11-11 | D02832 | | | | 3 | | | | SM00009 | | W | | ALL |
| 054R | 22 | | PH | 0-3 | 26-11-11 | D02832 | | | | 18 | | | | SM00009 | | W | | ALL |
| 055R | 22 | | PH | 3-0 | 26-11-11 | D10092 | | | | 55 | | | | D02832 | 6 | | | 050-099, 150-199 |
| 055R | 22 | | PH | 4-0 | 26-11-11 | D10092 | | | | 55 | | | | D02832 | 6 | | | 275-299 |
| 056R | 22 | | PH | 3-0 | 26-11-11 | D10092 | | | | 15 | | | | D02832 | 10 | | | 050-099, 150-199 |
| 056R | 22 | | PH | 4-0 | 26-11-11 | D10092 | | | | 15 | | | | D02832 | 10 | | | 275-299 |
| 057R | 22 | | PH | 3-0 | 26-11-11 | D10092 | | | | 45 | | | | D02832 | 16 | | | 050-099, 150-199 |
| 057R | 22 | | PH | 4-0 | 26-11-11 | D10092 | | | | 45 | | | | D02832 | 16 | | | 275-299 |
| 058R | 22 | | PH | 3-0 | 26-11-11 | D10092 | | | | 39 | | | | D02832 | 14 | | | 050-099, 150-199 |
| 058R | 22 | | PH | 4-0 | 26-11-11 | D10092 | | | | 39 | | | | D02832 | 14 | | | 275-299 |
| 061R | 22 | | PH | 3-0 | 26-11-12 | TB0276Y | | | A006 | BJ | | | | D02834 | 1 | | | 050-099 |
| 061R | 22 | | PH | 4-0 | 26-11-12 | TB0276Y | | | A006 | BJ | | | | D02834 | 1 | | | 150-199, 275-299 |
| 062R | 22 | | PH | 3-0 | 26-11-12 | TB0276Y | | | A006 | BJ | | | | D10092 | 34 | | | ALL |
| 063R | 22 | | PH | 0-3 | 26-11-12 | SM00019 | | | | | | | | D02834 | 3 | | | ALL |
| 064R | 22 | | PH | 0-3 | 26-11-12 | SM00019 | | | | | | | | D02834 | 18 | | | ALL |
| 065R | 22 | | PH | 3-0 | 26-11-12 | D10092 | | | | 54 | | | | D02834 | 6 | | | 050-099, 150-199 |
| 065R | 22 | | PH | 4-0 | 26-11-12 | D10092 | | | | 54 | | | | D02834 | 6 | | | 275-299 |
| 066R | 22 | | PH | 3-0 | 26-11-12 | D10092 | | | | 19 | | | | D02834 | 10 | | | 050-099, 150-199 |
| 066R | 22 | | PH | 4-0 | 26-11-12 | D10092 | | | | 19 | | | | D02834 | 10 | | | 275-299 |
| 067R | 22 | | PH | 3-0 | 26-11-12 | D10092 | | | | 28 | | | | D02834 | 16 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1082 | 286T1082 | | | FIRE DETECTION CARD FILE P54 (continued) | | | | | | | | | | | |
| 067R | 22 | | PH | | 4-0 | 26-11-12 | D10092 | | | | D02834 | | | | 275-299 |
| 068R | 22 | | PH | | 3-0 | 26-11-12 | D10092 | | | | D02834 | | | | 050-099, 150-199 |
| 068R | 22 | | PH | | 4-0 | 26-11-12 | D10092 | | | | D02834 | | | | 275-299 |
| 069R | 24 | | PP | | 4-0 | 26-16-11 | D10098 | | | | TB0276Z | 2 | BJ | | ALL |
| 070R | 24 | | PP | | 0-3 | 26-16-11 | SM00070 | | | | D10098 | | | | ALL |
| 071R | 24 | | PP | | 4-0 | 26-16-11 | TB0276Z | | 15 | | D10098 | | | | ALL |
| 072R | 22 | | PH | | 4-0 | 26-16-11 | TB0276Y | | A017 | | D10098 | | | | ALL |
| 073R | 24 | | PP | | 4-0 | 26-16-11 | TB0276Z | | 15 | | D10098 | | | | ALL |
| 074R | 24 | | PP | | 4-0 | 26-16-11 | TB0276Y | | A019 | | D10098 | | | | ALL |
| 075R | 24 | | PP | | 4-0 | 26-16-11 | TB0276Y | | A019 | | D10098 | | | | ALL |
| 076R | 24 | | PP | | 0-3 | 26-16-11 | SM00076 | | | | D10098 | | | | ALL |
| 079R | 24 | | PP | | 0-3 | 26-16-11 | SM00070 | | | | D10098 | | | | ALL |
| 080R | 24 | | PP | | 0-3 | 26-16-11 | SM00070 | | | | D10098 | | | | ALL |
| 081R | 22 | | PH | | 3-0 | 26-11-11 | TB0276Z | | 1 | | D10092 | | | | ALL |
| 082R | 22 | | PH | | 3-0 | 26-11-11 | TB0276Y | | A007 | | D10092 | | | | ALL |
| 083R | 22 | | PH | | 0-3 | 26-11-11 | SM00083 | | | | D10092 | | | | ALL |
| 084R | 22 | | PH | | 0-3 | 26-11-11 | SM00083 | | | | D10092 | | | | ALL |
| 085R | 22 | | PH | | 0-3 | 26-11-11 | SM00083 | | | | D10092 | | | | ALL |
| 086R | 22 | | PH | | 0-3 | 26-11-11 | SM00083 | | | | D10092 | | | | ALL |
| 087R | 22 | | PH | | 0-3 | 26-11-11 | D10092 | | 42 | | D10092 | | | | ALL |
| 088R | 22 | | PH | | 0-3 | 26-11-11 | SM00083 | | | | D10092 | | | | ALL |
| 089R | 22 | | PH | | 3-0 | 26-11-11 | TB0276Z | | 2 | | D10092 | | | | ALL |
| 090R | 22 | | PH | | 0-3 | 26-11-11 | SM00083 | | | | D10092 | | | | ALL |
| 093R | 24 | | PP | | 0-3 | 26-16-11 | SM00093 | | | | D10098 | | | | ALL |
| 094R | 24 | | PP | | 0-3 | 26-16-11 | SM00093 | | | | D10098 | | | | ALL |
| 095R | 24 | | PP | | 0-3 | 26-16-11 | SM00070 | | | | D10098 | | | | ALL |
| 096R | 24 | | PP | | 0-3 | 26-16-11 | SM00076 | | | | D10098 | | | | ALL |
| 097R | 24 | | PP | | 0-3 | 26-16-11 | SM00076 | | | | D10098 | | | | ALL |
| 098R | 24 | | PP | | 0-3 | 26-16-11 | SM00093 | | | | D10098 | | | | ALL |
| 100R | 24 | | PP | | 3-0 | 26-16-11 | SM00093 | | | | D10098 | | | | 050-099, 275-299 |
| 100R | 24 | | PP | | 1-0 | 26-16-11 | SM00093 | | | | D10098 | | | | 150-199 |
| 101R | 22 | | PH | | 4-0 | 26-11-11 | D07990J | | 1 | | TB0276Y | C005 | BJ | | ALL |
| 102R | 22 | | PH | | 4-0 | 26-11-11 | D07990J | | 2 | | SM00083 | | | | ALL |
| 104R | 22 | | PH | | 4-0 | 26-11-11 | D07990J | | 4 | | TB0276Y | A007 | BJ | | ALL |
| 105R | 22 | | PH | | 4-0 | 26-11-11 | D07990J | | 5 | | D10092 | | | | ALL |
| 106R | 22 | | PH | | 4-0 | 26-11-11 | D07990J | | 6 | | D02838 | | | | ALL |
| 107R | 22 | | PH | | 4-0 | 26-11-11 | D07990J | | 7 | | D02838 | | | | ALL |
| 108R | 22 | | PH | | 4-0 | 26-11-11 | D07990J | | 8 | | D02838 | | | | ALL |
| 109R | 22 | | PH | | 3-0 | 26-11-11 | D07990J | | 9 | | SM00109 | | | W | ALL |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 13

Mar 09/2006



| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1082 | 286T1082 | | | FIRE DETECTION CARD FILE P54 (continued) | | | | | | | | | | | |
| 110R | 22 | | PH | | 4-0 | 26-11-11 | D07990J | | | | D10092 | 10 | | | ALL |
| 111R | 22 | | PH | | 4-0 | 26-11-12 | D07990J | | | | TB0276Y | 11 | C006 | BJ | ALL |
| 112R | 22 | | PH | | 4-0 | 26-11-12 | D07990J | | | | SM00183 | 12 | | W | ALL |
| 114R | 22 | | PH | | 4-0 | 26-11-12 | D07990J | | | | D10092 | 14 | | | ALL |
| 115R | 22 | | PH | | 4-0 | 26-11-12 | D07990J | | | | D10092 | 15 | | | ALL |
| 116R | 22 | | PH | | 4-0 | 26-11-12 | D07990J | | | | D02840 | 16 | | | ALL |
| 117R | 22 | | PH | | 4-0 | 26-11-12 | D07990J | | | | D02840 | 17 | | | ALL |
| 118R | 22 | | PH | | 4-0 | 26-11-12 | D07990J | | | | D02840 | 18 | | | ALL |
| 119R | 22 | | PH | | 3-0 | 26-11-12 | D07990J | | | | SM00119 | 19 | | W | ALL |
| 120R | 22 | | PH | | 4-0 | 49-61-11 | D07990J | | | | TB0276Z | 20 | 14 | BJ | ALL |
| 121R | 22 | | PH | | 4-0 | 26-15-11 | D07990J | | | | TB0276Y | 21 | C007 | BJ | ALL |
| 122R | 22 | | PH | | 4-0 | 26-11-11 | D07990J | | | | TB0276Z | 22 | 1 | BJ | ALL |
| 123R | 22 | | PH | | 4-0 | 26-11-11 | D07990J | | | | TB0276Z | 23 | 2 | BJ | ALL |
| 125R | 22 | | PH | | 3-0 | 26-15-11 | D07990J | | | | D10096 | 25 | 47 | | ALL |
| 126R | 22 | | PH | | 4-0 | 26-15-11 | D07990J | | | | D02850 | 26 | 21 | | ALL |
| 127R | 22 | | PH | | 4-0 | 26-15-11 | D07990J | | | | D02850 | 27 | 19 | | ALL |
| 128R | 22 | | PH | | 4-0 | 26-15-11 | D07990J | | | | D02850 | 28 | 20 | | ALL |
| 129R | 22 | | PH | | 3-0 | 26-15-11 | D07990J | | | | SM00129 | 29 | | W | ALL |
| 130R | 22 | | PH | | 3-0 | 26-15-11 | D07990J | | | | D10096 | 30 | 10 | | ALL |
| 131R | 24 | | PP | | 4-0 | 26-16-11 | D07990J | | | | TB0276Z | 31 | 15 | BJ | ALL |
| 132R | 24 | | PP | | 4-0 | 26-16-11 | D07990J | | | | SM00093 | 32 | | W | ALL |
| 133R | 24 | | PP | | 4-0 | 26-16-11 | D07990J | | | | TB0276Z | 33 | 15 | BJ | ALL |
| 134R | 24 | | PP | | 4-0 | 26-16-11 | D07990J | | | | TB0276Z | 34 | 15 | BJ | ALL |
| 135R | 24 | | PP | | 4-0 | 26-16-11 | D07990J | | | | D10098 | 35 | 55 | | ALL |
| 136R | 24 | | PP | | 4-0 | 26-16-11 | D07990J | | | | D10098 | 36 | 39 | | ALL |
| 137R | 24 | | PP | | 4-0 | 26-16-11 | D07990J | | | | D10098 | 37 | 54 | | ALL |
| 138R | 24 | | PP | | 4-0 | 26-16-11 | D07990J | | | | D10098 | 38 | 65 | | ALL |
| 139R | 22 | | PH | | 4-0 | 26-16-11 | D07990J | | | | TB0276Y | 39 | A017 | BJ | ALL |
| 143R | 24 | | PP | | 4-0 | 26-16-11 | D07990J | | | | TB0276Y | 43 | A019 | BJ | ALL |
| 146R | 22 | | PH | | 3-0 | 26-17-11 | D07990J | | | | D02842 | 46 | 15 | | ALL |
| 147R | 22 | | PH | | 3-0 | 26-17-11 | D07990J | | | | D02842 | 47 | 29 | | ALL |
| 151R | 22 | | PH | | 4-0 | 26-11-11 | TB0276Y | C005 | BJ | | D02838 | 1 | 1 | | ALL |
| 152R | 22 | | PH | | 3-0 | 26-11-11 | TB0276Y | C005 | BJ | | D10092 | 1 | 1 | | ALL |
| 153R | 22 | | PH | | 0-3 | 26-11-11 | SM00109 | | W | | D02838 | 3 | 3 | | ALL |
| 154R | 22 | | PH | | 0-3 | 26-11-11 | SM00109 | | W | | D02838 | 18 | 18 | | ALL |
| 155R | 22 | | PH | | 2-0 | 26-11-11 | D10092 | | | 44 | D02838 | 6 | 6 | | ALL |
| 156R | 22 | | PH | | 2-0 | 26-11-11 | D10092 | | | 48 | D02838 | 10 | 10 | | ALL |
| 157R | 22 | | PH | | 2-0 | 26-11-11 | D10092 | | | 3 | D02838 | 16 | 16 | | ALL |
| 158R | 22 | | PH | | 2-0 | 26-11-11 | D10092 | | | 9 | D02838 | 14 | 14 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1082 | 286T1082 | | | FIRE DETECTION CARD FILE P54 (continued) | | | | | | | | | | | |
| 161R | 22 | | PH | | 3-0 | 26-11-12 | TB0276Y | C006 | BJ | | D02840 | | 1 | | ALL |
| 162R | 22 | | PH | | 3-0 | 26-11-12 | TB0276Y | C006 | BJ | | D10092 | | 33 | | ALL |
| 163R | 22 | | PH | | 0-3 | 26-11-12 | D02840 | | | 3 | SM00119 | | | W | ALL |
| 164R | 22 | | PH | | 0-3 | 26-11-12 | D02840 | | | 18 | SM00119 | | | W | ALL |
| 165R | 22 | | PH | | 3-0 | 26-11-12 | D10092 | | | 30 | D02840 | | 6 | | ALL |
| 166R | 22 | | PH | | 3-0 | 26-11-12 | D10092 | | | 52 | D02840 | | 10 | | ALL |
| 167R | 22 | | PH | | 3-0 | 26-11-12 | D10092 | | | 27 | D02840 | | 16 | | ALL |
| 168R | 22 | | PH | | 3-0 | 26-11-12 | D10092 | | | 29 | D02840 | | 14 | | ALL |
| 171R | 22 | | PH | | 4-0 | 26-15-11 | TB0276Y | C007 | BJ | | D02850 | | 1 | | ALL |
| 172R | 22 | | PH | | 4-0 | 26-15-11 | TB0276Y | C007 | BJ | | D10096 | | 1 | | ALL |
| 173R | 22 | | PH | | 0-3 | 26-15-11 | D02850 | | | 3 | SM00129 | | | W | ALL |
| 174R | 22 | | PH | | 0-3 | 26-15-11 | D02850 | | | 18 | SM00129 | | | W | ALL |
| 175R | 22 | | PH | | 2-0 | 26-15-11 | D10096 | | | 44 | D02850 | | 6 | | ALL |
| 176R | 22 | | PH | | 2-0 | 26-15-11 | D10096 | | | 48 | D02850 | | 10 | | ALL |
| 177R | 22 | | PH | | 2-0 | 26-15-11 | D10096 | | | 3 | D02850 | | 16 | | ALL |
| 178R | 22 | | PH | | 2-0 | 26-15-11 | D10096 | | | 9 | D02850 | | 14 | | ALL |
| 183R | 22 | | PH | | 0-3 | 26-11-12 | D10092 | | | 51 | SM00183 | | | W | ALL |
| 184R | 22 | | PH | | 0-3 | 26-11-12 | D10092 | | | 18 | SM00183 | | | W | ALL |
| 185R | 22 | | PH | | 0-3 | 26-11-12 | D10092 | | | 32 | SM00183 | | | W | ALL |
| 186R | 22 | | PH | | 0-3 | 26-11-12 | D10092 | | | 20 | SM00183 | | | W | ALL |
| 187R | 22 | | PH | | 0-3 | 26-11-12 | D10092 | | | 53 | D10092 | | 60 | | ALL |
| 188R | 22 | | PH | | 0-3 | 26-11-12 | D10092 | | | 21 | SM00183 | | | W | ALL |
| 190R | 22 | | PH | | 0-3 | 26-11-12 | D10092 | | | 25 | SM00183 | | | W | ALL |
| 501R | 22 | | PH | | 4-0 | 26-11-21 | D07996J | | | 1 | TB0276Y | A008 | BJ | | ALL |
| 502 | 24 | | PK | | 4-0 | 31-51-21 | D07996J | | | 2 | TB0276Z | 14 | BJ | | ALL |
| 503 | 24 | | PK | | 4-0 | 31-51-21 | D07996J | | | 3 | TB0276Y | A020 | BJ | | ALL |
| 506R | 22 | | PH | | 3-0 | 26-11-21 | D07996J | | | 6 | D02846 | | 19 | | ALL |
| 507R | 22 | | PH | | 3-0 | 26-11-21 | D07996J | | | 7 | D02846 | | 21 | | ALL |
| 508R | 22 | | PH | | 3-0 | 26-11-21 | D07996J | | | 8 | D02846 | | 20 | | ALL |
| 509R | 22 | | PH | | 3-0 | 26-11-21 | D07996J | | | 9 | SM00509 | | | W | ALL |
| 511R | 22 | | PH | | 5-0 | 26-11-22 | D07996J | | | 11 | TB0276Y | A009 | BJ | | 050-099, 275-299 |
| 511R | 22 | | PH | | 4-0 | 26-11-22 | D07996J | | | 11 | TB0276Y | A009 | BJ | | 150-199 |
| 516R | 22 | | PH | | 3-0 | 26-11-22 | D07996J | | | 16 | D02848 | | 21 | | ALL |
| 517R | 22 | | PH | | 3-0 | 26-11-22 | D07996J | | | 17 | D02848 | | 19 | | ALL |
| 518R | 22 | | PH | | 3-0 | 26-11-22 | D07996J | | | 18 | D02848 | | 20 | | ALL |
| 519R | 22 | | PH | | 3-0 | 26-11-22 | D07996J | | | 19 | SM00519 | | | W | ALL |
| 551R | 22 | | PH | | 4-0 | 26-11-21 | TB0276Y | A008 | BJ | | D02846 | | 1 | | ALL |
| 552R | 22 | | PH | | 4-0 | 26-11-21 | TB0276Y | A008 | BJ | | D10094 | | 2 | | ALL |
| 553R | 22 | | PH | | 0-3 | 26-11-21 | D02846 | | | 3 | SM00509 | | | W | ALL |

WIRE LIST

D280T132

91-21-11
 Section W1080
 Page 15
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1082 | 286T1082 | | | FIRE DETECTION CARD FILE P54 (continued) | | | | | | | | | | | | | |
| 554R | 22 | | PH | 0-3 | 26-11-21 | D02846 | | 18 | | | | | SM00509 | | W | | ALL |
| 555R | 22 | | PH | 2-0 | 26-11-21 | D10094 | | 55 | | | | | D02846 | 6 | | | ALL |
| 556R | 22 | | PH | 2-0 | 26-11-21 | D10094 | | 15 | | | | | D02846 | 10 | | | ALL |
| 557R | 22 | | PH | 2-0 | 26-11-21 | D10094 | | 45 | | | | | D02846 | 16 | | | ALL |
| 558R | 22 | | PH | 2-0 | 26-11-21 | D10094 | | 39 | | | | | D02846 | 14 | | | ALL |
| 561R | 22 | | PH | 4-0 | 26-11-22 | TB0276Y | A009 | | BJ | | | | D02848 | 1 | | | ALL |
| 562R | 22 | | PH | 4-0 | 26-11-22 | TB0276Y | A009 | | BJ | | | | D10094 | 34 | | | ALL |
| 563R | 22 | | PH | 0-3 | 26-11-22 | D02848 | | 3 | | | | | SM00519 | | W | | ALL |
| 564R | 22 | | PH | 0-3 | 26-11-22 | D02848 | | 18 | | | | | SM00519 | | W | | ALL |
| 565R | 22 | | PH | 2-0 | 26-11-22 | D10094 | | 54 | | | | | D02848 | 6 | | | ALL |
| 566R | 22 | | PH | 2-0 | 26-11-22 | D10094 | | 19 | | | | | D02848 | 10 | | | ALL |
| 567R | 22 | | PH | 2-0 | 26-11-22 | D10094 | | 28 | | | | | D02848 | 16 | | | ALL |
| 568R | 22 | | PH | 2-0 | 26-11-22 | D10094 | | 65 | | | | | D02848 | 14 | | | ALL |
| 570R | 24 | | PP | 0-3 | 26-16-11 | SM00570 | | | | W | | | D10098 | 58 | | | ALL |
| 571R | 24 | | PP | 4-0 | 26-16-11 | TB0276Z | | 16 | | BJ | | | D10098 | 2 | | | ALL |
| 572R | 22 | | PH | 4-0 | 26-16-11 | TB0276Y | C017 | | | BJ | | | D10098 | 23 | | | ALL |
| 573R | 24 | | PP | 4-0 | 26-16-11 | TB0276Z | | 16 | | BJ | | | D10098 | 34 | | | ALL |
| 574R | 24 | | PP | 4-0 | 26-16-11 | TB0276Z | | 1 | | BJ | | | D10098 | 8 | | | ALL |
| 575R | 24 | | PP | 4-0 | 26-16-11 | TB0276Z | | 1 | | BJ | | | D10098 | 24 | | | ALL |
| 576R | 24 | | PP | 0-3 | 26-16-11 | SM00576 | | | | W | | | D10098 | 38 | | | ALL |
| 579R | 24 | | PP | 0-3 | 26-16-11 | SM00570 | | | | W | | | D10098 | 19 | | | ALL |
| 580R | 24 | | PP | 0-3 | 26-16-11 | SM00570 | | | | W | | | D10098 | 52 | | | ALL |
| 581R | 22 | | PH | 4-0 | 26-11-21 | TB0276Z | | 1 | | BJ | | | D10094 | 8 | | | ALL |
| 582R | 22 | | PH | 4-0 | 26-11-21 | TB0276Y | A010 | | | BJ | | | D10094 | 11 | | | ALL |
| 583R | 22 | | PH | 0-3 | 26-11-21 | SM00583 | | | | W | | | D10094 | 49 | | | ALL |
| 584R | 22 | | PH | 0-3 | 26-11-21 | SM00583 | | | | W | | | D10094 | 16 | | | ALL |
| 585R | 22 | | PH | 0-3 | 26-11-21 | SM00583 | | | | W | | | D10094 | 50 | | | ALL |
| 586R | 22 | | PH | 0-3 | 26-11-21 | SM00583 | | | | W | | | D10094 | 14 | | | ALL |
| 587R | 22 | | PH | 0-3 | 26-11-21 | D10094 | | 13 | | | | | D10094 | 42 | | | ALL |
| 588R | 22 | | PH | 0-3 | 26-11-21 | SM00583 | | | | W | | | D10094 | 46 | | | ALL |
| 589R | 22 | | PH | 4-0 | 26-11-21 | TB0276Z | | 2 | | BJ | | | D10094 | 7 | | | ALL |
| 590R | 22 | | PH | 0-3 | 26-11-21 | SM00583 | | | | W | | | D10094 | 17 | | | ALL |
| 593R | 24 | | PP | 0-3 | 26-16-11 | SM00593 | | | | W | | | D10098 | 51 | | | ALL |
| 594R | 24 | | PP | 0-3 | 26-16-11 | SM00593 | | | | W | | | D10098 | 18 | | | ALL |
| 595R | 24 | | PP | 0-3 | 26-16-11 | SM00570 | | | | W | | | D10098 | 32 | | | ALL |
| 596R | 24 | | PP | 0-3 | 26-16-11 | SM00576 | | | | W | | | D10098 | 20 | | | ALL |
| 597R | 24 | | PP | 0-3 | 26-16-11 | SM00576 | | | | W | | | D10098 | 53 | | | ALL |
| 598R | 24 | | PP | 0-3 | 26-16-11 | SM00593 | | | | W | | | D10098 | 21 | | | ALL |
| 600R | 24 | | PP | 0-3 | 26-16-11 | SM00593 | | | | W | | | D10098 | 25 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1082 | 286T1082 | | | FIRE DETECTION CARD FILE P54 (continued) | | | | | | | | | | | |
| 601R | 22 | | PH | | 4-0 | 26-11-21 | D07994J | | | | TB0276Y | C008 | BJ | | ALL |
| 602R | 22 | | PH | | 4-0 | 26-11-21 | D07994J | | | | SM00583 | | W | | 050-099, 275-299 |
| 602R | 22 | | PH | | 3-0 | 26-11-21 | D07994J | | | | SM00583 | | W | | 150-199 |
| 604R | 22 | | PH | | 4-0 | 26-11-21 | D07994J | | | | TB0276Y | A010 | BJ | | ALL |
| 605R | 22 | | PH | | 3-0 | 26-11-21 | D07994J | | | | D10094 | 47 | | | ALL |
| 606R | 22 | | PH | | 3-0 | 26-11-21 | D07994J | | | | D02852 | 19 | | | ALL |
| 607R | 22 | | PH | | 3-0 | 26-11-21 | D07994J | | | | D02852 | 21 | | | ALL |
| 608R | 22 | | PH | | 3-0 | 26-11-21 | D07994J | | | | D02852 | 20 | | | ALL |
| 609R | 22 | | PH | | 3-0 | 26-11-21 | D07994J | | | | SM00609 | | W | | ALL |
| 610R | 22 | | PH | | 3-0 | 26-11-21 | D07994J | | | | D10094 | 10 | | | ALL |
| 611R | 22 | | PH | | 4-0 | 26-11-22 | D07994J | | | | TB0276Y | C009 | BJ | | ALL |
| 612R | 22 | | PH | | 4-0 | 26-11-22 | D07994J | | | | SM00683 | | W | | 050-099, 275-299 |
| 612R | 22 | | PH | | 3-0 | 26-11-22 | D07994J | | | | SM00683 | | W | | 150-199 |
| 614R | 22 | | PH | | 3-0 | 26-11-22 | D07994J | | | | D10094 | 23 | | | ALL |
| 615R | 22 | | PH | | 3-0 | 26-11-22 | D07994J | | | | D10094 | 22 | | | ALL |
| 616R | 22 | | PH | | 3-0 | 26-11-22 | D07994J | | | | D02854 | 21 | | | ALL |
| 617R | 22 | | PH | | 3-0 | 26-11-22 | D07994J | | | | D02854 | 19 | | | ALL |
| 618R | 22 | | PH | | 3-0 | 26-11-22 | D07994J | | | | D02854 | 20 | | | ALL |
| 619R | 22 | | PH | | 3-0 | 26-11-22 | D07994J | | | | SM00619 | | W | | ALL |
| 620R | 22 | | PH | | 4-0 | 26-15-12 | D07994J | | | | TB0276Z | 14 | BJ | | ALL |
| 621R | 22 | | PH | | 4-0 | 26-15-11 | D07994J | | | | TB0276Y | C010 | BJ | | ALL |
| 622R | 22 | | PH | | 4-0 | 26-15-11 | D07994J | | | | SM00693 | | W | | 050-099, 275-299 |
| 622R | 22 | | PH | | 3-0 | 26-15-11 | D07994J | | | | SM00693 | | W | | 150-199 |
| 624R | 22 | | PH | | 4-0 | 26-15-11 | D07994J | | | | TB0276Z | 14 | BJ | | ALL |
| 626R | 22 | | PH | | 3-0 | 26-15-11 | D07994J | | | | D02836 | 21 | | | ALL |
| 627R | 22 | | PH | | 3-0 | 26-15-11 | D07994J | | | | D02836 | 19 | | | ALL |
| 628R | 22 | | PH | | 3-0 | 26-15-11 | D07994J | | | | D02836 | 20 | | | ALL |
| 629R | 22 | | PH | | 3-0 | 26-15-11 | D07994J | | | | SM00629 | | W | | ALL |
| 631R | 24 | | PP | | 4-0 | 26-16-11 | D07994J | | | | TB0276Z | 16 | BJ | | ALL |
| 632R | 24 | | PP | | 4-0 | 26-16-11 | D07994J | | | | SM00593 | | W | | ALL |
| 633R | 24 | | PP | | 4-0 | 26-16-11 | D07994J | | | | TB0276Z | 16 | BJ | | ALL |
| 634R | 24 | | PP | | 4-0 | 26-16-11 | D07994J | | | | TB0276Z | 16 | BJ | | ALL |
| 635R | 24 | | PP | | 4-0 | 26-16-11 | D07994J | | | | D10098 | 44 | | | ALL |
| 636R | 24 | | PP | | 4-0 | 26-16-11 | D07994J | | | | D10098 | 3 | | | ALL |
| 637R | 24 | | PP | | 4-0 | 26-16-11 | D07994J | | | | D10098 | 30 | | | ALL |
| 638R | 24 | | PP | | 4-0 | 26-16-11 | D07994J | | | | D10098 | 27 | | | ALL |
| 639R | 22 | | PH | | 4-0 | 26-16-11 | D07994J | | | | TB0276Y | C017 | BJ | | ALL |
| 643R | 24 | | PP | | 4-0 | 26-16-11 | D07994J | | | | D10098 | 10 | | | ALL |
| 644R | 22 | | PH | | 4-0 | 26-17-11 | D07994J | | | | D02842 | 17 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W1080
 Page 17
 Mar 09/2006



| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1082 | 286T1082 | | | FIRE DETECTION CARD FILE P54 (continued) | | | | | | | | | | | |
| 645R | 22 | | PH | | 4-0 | 26-17-11 | D07994J | | | | D02842 | 19 | | | ALL |
| 648R | 22 | | PH | | 4-0 | 26-17-11 | D07994J | | | | D02842 | 34 | | | ALL |
| 649R | 22 | | PH | | 4-0 | 26-17-11 | D07994J | | | | TB0276Z | 1 | BJ | | ALL |
| 651R | 22 | | PH | | 4-0 | 26-11-21 | TB0276Y | C008 | BJ | | D02852 | 1 | | | ALL |
| 652R | 22 | | PH | | 4-0 | 26-11-21 | TB0276Y | C008 | BJ | | D10094 | 1 | | | ALL |
| 653R | 22 | | PH | | 0-3 | 26-11-21 | D02852 | | | | SM00609 | | W | | ALL |
| 654R | 22 | | PH | | 0-3 | 26-11-21 | D02852 | | | | SM00609 | | W | | ALL |
| 655R | 22 | | PH | | 2-0 | 26-11-21 | D10094 | | | | D02852 | 6 | | | ALL |
| 656R | 22 | | PH | | 2-0 | 26-11-21 | D10094 | | | | D02852 | 10 | | | ALL |
| 657R | 22 | | PH | | 2-0 | 26-11-21 | D10094 | | | | D02852 | 16 | | | ALL |
| 658R | 22 | | PH | | 2-0 | 26-11-21 | D10094 | | | | D02852 | 14 | | | ALL |
| 661R | 22 | | PH | | 3-0 | 26-11-22 | TB0276Y | C009 | BJ | | D02854 | 1 | | | ALL |
| 662R | 22 | | PH | | 4-0 | 26-11-22 | TB0276Y | C009 | BJ | | D10094 | 33 | | | ALL |
| 663R | 22 | | PH | | 0-3 | 26-11-22 | D02854 | | | | SM00619 | | W | | ALL |
| 664R | 22 | | PH | | 0-3 | 26-11-22 | D02854 | | | | SM00619 | | W | | ALL |
| 665R | 22 | | PH | | 3-0 | 26-11-22 | D10094 | | | | D02854 | 6 | | | ALL |
| 666R | 22 | | PH | | 3-0 | 26-11-22 | D10094 | | | | D02854 | 10 | | | ALL |
| 667R | 22 | | PH | | 3-0 | 26-11-22 | D10094 | | | | D02854 | 16 | | | ALL |
| 668R | 22 | | PH | | 3-0 | 26-11-22 | D10094 | | | | D02854 | 14 | | | ALL |
| 671R | 22 | | PH | | 3-0 | 26-15-11 | TB0276Y | C010 | BJ | | D02836 | 1 | | | ALL |
| 672R | 22 | | PH | | 4-0 | 26-15-11 | TB0276Y | C010 | BJ | | D10096 | 2 | | | ALL |
| 673R | 22 | | PH | | 0-3 | 26-15-11 | D02836 | | | | SM00629 | | W | | ALL |
| 674R | 22 | | PH | | 0-3 | 26-15-11 | D02836 | | | | SM00629 | | W | | ALL |
| 675R | 22 | | PH | | 3-0 | 26-15-11 | D10096 | | | | D02836 | 6 | | | ALL |
| 676R | 22 | | PH | | 3-0 | 26-15-11 | D10096 | | | | D02836 | 10 | | | ALL |
| 677R | 22 | | PH | | 3-0 | 26-15-11 | D10096 | | | | D02836 | 16 | | | ALL |
| 678R | 22 | | PH | | 3-0 | 26-15-11 | D10096 | | | | D02836 | 14 | | | ALL |
| 683R | 22 | | PH | | 0-3 | 26-11-22 | D10094 | | | | SM00683 | | W | | ALL |
| 684R | 22 | | PH | | 0-3 | 26-11-22 | D10094 | | | | SM00683 | | W | | ALL |
| 685R | 22 | | PH | | 0-3 | 26-11-22 | D10094 | | | | SM00683 | | W | | ALL |
| 686R | 22 | | PH | | 0-3 | 26-11-22 | D10094 | | | | SM00683 | | W | | ALL |
| 687R | 22 | | PH | | 0-3 | 26-11-22 | D10094 | | | | D10094 | 60 | | | ALL |
| 688R | 22 | | PH | | 0-3 | 26-11-22 | D10094 | | | | SM00683 | | W | | ALL |
| 690R | 22 | | PH | | 0-3 | 26-11-22 | D10094 | | | | SM00683 | | W | | ALL |
| 691R | 22 | | PH | | 4-0 | 26-15-11 | D10096 | | | | TB0276Z | 1 | BJ | | ALL |
| 692R | 22 | | PH | | 4-0 | 26-15-11 | D10096 | | | | TB0276Z | 14 | BJ | | ALL |
| 693R | 22 | | PH | | 0-3 | 26-15-11 | D10096 | | | | SM00693 | | W | | ALL |
| 694R | 22 | | PH | | 0-3 | 26-15-11 | D10096 | | | | SM00693 | | W | | ALL |
| 695R | 22 | | PH | | 0-3 | 26-15-11 | D10096 | | | | SM00693 | | W | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 18

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1082 | 286T1082 | | | FIRE DETECTION CARD FILE P54 (continued) | | | | | | | | | | | |
| 696R | 22 | | PH | 0-3 | 26-15-11 | D10096 | | 14 | | SM00693 | | | W | | ALL |
| 697R | 22 | | PH | 0-3 | 26-15-11 | D10096 | | 13 | | D10096 | | 42 | | | ALL |
| 698R | 22 | | PH | 0-3 | 26-15-11 | D10096 | | 46 | | SM00693 | | | W | | ALL |
| 699R | 22 | | PH | 4-0 | 26-15-11 | D10096 | | 7 | | TB0276Z | | 2 | BJ | | ALL |
| 700R | 22 | | PH | 0-3 | 26-15-11 | D10096 | | 17 | | SM00693 | | | W | | ALL |
| 702R | 22 | | PH | 4-0 | 26-11-11 | D05546J | | 2 | | D10092 | | 5 | | | ALL |
| 703R | 22 | | PH | 4-0 | 26-11-12 | D05546J | | 3 | | D10092 | | 63 | | | ALL |
| 704R | 22 | | PH | 3-0 | 26-11-21 | D05546J | | 4 | | D10094 | | 5 | | | ALL |
| 705R | 22 | | PH | 3-0 | 26-11-22 | D05546J | | 5 | | D10094 | | 63 | | | ALL |
| 706R | 22 | | PH | 3-0 | 26-15-11 | D05546J | | 6 | | D10096 | | 5 | | | ALL |
| 707R | 22 | | PH | 4-0 | 26-11-11 | D05546J | | 7 | | TB0276Y | A007 | BJ | | | ALL |
| 708R | 22 | | PH | 4-0 | 26-11-12 | D05546J | | 8 | | D10092 | | 24 | | | ALL |
| 710R | 22 | | PH | 4-0 | 26-11-11 | D05546J | | 10 | | TB0276Z | | 2 | BJ | | ALL |
| 712R | 24 | | PP | 4-0 | 26-16-11 | D05546J | | 12 | | TB0276Y | A017 | BJ | | | ALL |
| 713R | 24 | | PP | 3-0 | 26-16-11 | D05546J | | 13 | | D10098 | | 5 | | | ALL |
| 714R | 24 | | PP | 3-0 | 26-16-11 | D05546J | | 14 | | D10098 | | 63 | | | ALL |
| 722R | 22 | | PH | 4-0 | 26-11-11 | D05548J | | 2 | | D10092 | | 36 | | | ALL |
| 723R | 22 | | PH | 4-0 | 26-11-12 | D05548J | | 3 | | D10092 | | 62 | | | ALL |
| 724R | 22 | | PH | 3-0 | 26-11-21 | D05548J | | 4 | | D10094 | | 36 | | | ALL |
| 725R | 22 | | PH | 3-0 | 26-11-22 | D05548J | | 5 | | D10094 | | 62 | | | ALL |
| 726R | 22 | | PH | 3-0 | 26-15-11 | D05548J | | 6 | | D10096 | | 36 | | | ALL |
| 727R | 22 | | PH | 4-0 | 26-11-21 | D05548J | | 7 | | TB0276Y | A010 | BJ | | | ALL |
| 728R | 22 | | PH | 3-0 | 26-11-22 | D05548J | | 8 | | D10094 | | 24 | | | ALL |
| 729R | 22 | | PH | 4-0 | 26-15-11 | D05548J | | 9 | | TB0276Z | | 14 | BJ | | ALL |
| 732R | 24 | | PP | 4-0 | 26-16-11 | D05548J | | 12 | | TB0276Y | C017 | BJ | | | ALL |
| 733R | 24 | | PP | 4-0 | 26-16-11 | D05548J | | 13 | | D10098 | | 36 | | | ALL |
| 734R | 24 | | PP | 4-0 | 26-16-11 | D05548J | | 14 | | D10098 | | 62 | | | ALL |
| 735R | 22 | | PH | 4-0 | 26-17-11 | D05548J | | 15 | | TB0276Y | A020 | BJ | | | ALL |
| 805R | 22 | | PH | 4-0 | 26-18-11 | D04002J | | 5 | | D02842 | | 6 | | | ALL |
| 806R | 22 | | PH | 4-0 | 26-18-11 | D04002J | | 6 | | D02842 | | 1 | | | ALL |
| 807R | 22 | | PH | 4-0 | 26-18-21 | D04002J | | 7 | | D02842 | | 12 | | | ALL |
| 808R | 22 | | PH | 4-0 | 26-18-21 | D04002J | | 8 | | D02842 | | 8 | | | ALL |
| 809R | 22 | | PH | 4-0 | 26-18-31 | D04002J | | 9 | | D02842 | | 27 | | | ALL |
| 810R | 22 | | PH | 4-0 | 26-18-31 | D04002J | | 10 | | D02842 | | 22 | | | ALL |
| 811 | 24 | | PK | 4-0 | 31-51-21 | D04002J | | 11 | | TB0276Y | A017 | BJ | | | ALL |
| 812 | 24 | | PK | 4-0 | 31-51-21 | D04002J | | 12 | | TB0276Y | A007 | BJ | | | ALL |
| 842R | 22 | | PH | 4-0 | 26-17-11 | D02842 | | 32 | | TB0276Y | A020 | BJ | | | ALL |
| 853R | 22 | | PH | 4-0 | 26-18-11 | D05540J | | 3 | | D02842 | | 3 | | | 050-099, 150-199 |
| 853R | 22 | | PH | 4-0 | 26-18-11 | D02842 | | 3 | | D05540J | | 3 | | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1080
Page 19
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1082 | 286T1082 | | | FIRE DETECTION CARD FILE P54 (continued) | | | | | | | | | | | | |
| 854R | 22 | | PH | 4-0 | 26-18-21 | D05540J | | 4 | | | | | D02842 | 10 | | ALL |
| 855R | 22 | | PH | 4-0 | 26-18-31 | D05540J | | 5 | | | | | D02842 | 24 | | ALL |
| PA1 | | | | 0-0 | 99-99-99 | D02832 | | 2 | | | | | D02832 | 5 | | ALL |
| PA2 | | | | 0-0 | 99-99-99 | D02834 | | 2 | | | | | D02834 | 5 | | ALL |
| PA3 | | | | 0-0 | 99-99-99 | D02836 | | 2 | | | | | D02836 | 5 | | ALL |
| PA4 | | | | 0-0 | 99-99-99 | D02838 | | 2 | | | | | D02838 | 5 | | ALL |
| PA5 | | | | 0-0 | 99-99-99 | D02840 | | 2 | | | | | D02840 | 5 | | ALL |
| PA6 | | | | 0-0 | 99-99-99 | D02842 | | 38 | | | | | D02842 | 63 | | ALL |
| PA7 | | | | 0-0 | 99-99-99 | D02846 | | 2 | | | | | D02846 | 5 | | ALL |
| PA8 | | | | 0-0 | 99-99-99 | D02848 | | 2 | | | | | D02848 | 5 | | ALL |
| PA9 | | | | 0-0 | 99-99-99 | D02850 | | 2 | | | | | D02850 | 5 | | ALL |
| PB1 | | | | 0-0 | 99-99-99 | D02852 | | 2 | | | | | D02852 | 5 | | ALL |
| PB2 | | | | 0-0 | 99-99-99 | D02854 | | 2 | | | | | D02854 | 5 | | ALL |
| PB3 | | | | 1-0 | 99-99-99 | D10092 | | 35 | | | | | D10092 | 66 | | ALL |
| PB4 | | | | 1-0 | 99-99-99 | D10094 | | 35 | | | | | D10094 | 66 | | ALL |
| PB5 | | | | 1-0 | 99-99-99 | D10096 | | 35 | | | | | D10096 | 66 | | ALL |
| PB6 | | | | 1-0 | 99-99-99 | D10098 | | 35 | | | | | D10098 | 66 | | ALL |
| W1083 | 286T1083 | | | E2-2 SHELF,MKR BCN COAX | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-32-11 | D00329C | | = C5 | | | | | D04069P | = C1 | | ALL |
| 01CX | | | BR A | 4-3 | 34-32-11 | D00329C | | 5 | | | | | D04069P | = A1 | | ALL |
| W1084 | 286T1084 | | | SHELF E1-1 INTEGRATION | | | | | | | | | | | | |
| 001 | 24 | | PK | 5-4 | 32-42-11 | TB0101G | | 97 | 2 | | | | D04674P | 8 | | ALL |
| 002 | 24 | | PK | 3-0 | 32-42-11 | TB0101G | | 94 | 2 | | | | D04656P | 14 | | ALL |
| 003 | 24 | | PK | 2-11 | 32-42-11 | TB0101G | | 89 | 2 | | | | D04874P | 1 | | ALL |
| 004 | 24 | | PK | 2-10 | 32-42-11 | TB0101G | | 93 | 2 | | | | D04874P | 2 | | ALL |
| 005 | 24 | | PK | 5-5 | 32-42-11 | D02372A | | | | D01 | | | D04930P | 11 | | ALL |
| 006 | 24 | | PV | 5-5 | 32-42-11 | D02372B | | | | D01 | | | D04930P | 15 | | ALL |
| 006Z | | | | 0-0 | 32-42-11 | D02372B | | | | DED | | | D04930P | DED | | ALL |
| 007 | 24 | | PK | 5-5 | 32-42-11 | D02372B | | | | A01 | | | D04930P | 12 | | ALL |
| 008 | 24 | | PK | 5-5 | 32-42-11 | D02372B | | | | A03 | | | D04930P | 14 | | ALL |
| 009 | 24 | | PK | 5-5 | 32-42-11 | D02372B | | | | B15 | | | D04930P | 16 | | ALL |
| 010 | 24 | | PK | 6-0 | 32-42-11 | D02372A | | | | B01 | | | D04908P | 5 | | ALL |
| 011 | 24 | | PK | 6-0 | 32-42-11 | D02372A | | | | B03 | | | D04908P | 7 | | ALL |
| 012 | 24 | | PK | 6-0 | 32-42-11 | D02372A | | | | A15 | | | D04908P | 9 | | ALL |
| 013 | 22 | | PA | 2-1 | 32-42-11 | D02372B | | | | C13 | | | GDX0014 | D.. 2 | | ALL |
| 014 | 22 | | PA | 2-1 | 32-42-11 | D02372B | | | | C02 | | | GDX0014 | D.. 2 | | ALL |
| 015 | 22 | | PA | 2-1 | 32-42-11 | D02372A | | | | C06 | | | GDX0014 | D.. 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 20

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1084 | 286T1084 | | | SHELF E1-1 INTEGRATION (continued) | | | | | | | | | | | |
| 016 | 22 | | PA | | 2-1 | 32-42-11 | D02372A | | | | GDX0014 | D.. | 2 | | ALL |
| 017 | 22 | | PA | | 2-1 | 32-42-11 | D02372A | | | | GDX0014 | D.. | 2 | | ALL |
| 018 | 22 | | PA | | 2-1 | 32-42-12 | D02372B | | | | GDX0014 | D.. | 2 | | ALL |
| 019 | 22 | | PA | | 2-1 | 32-42-11 | D02372A | | | | GDX0014 | S.. | 2 | | ALL |
| 020 | 20 | | UA | | 2-1 | 32-42-11 | D02372B | | | | GDX0014 | S.. | 2 | | ALL |
| 021 | 20 | | UA | | 2-1 | 32-42-11 | D02372A | | | | GDX0014 | S.. | 2 | | ALL |
| 022 | 24 | | PK | | 2-8 | 32-42-11 | D02372A | | | | D05210P | | 11 | | ALL |
| 024 | 24 | | PK | | 2-8 | 32-42-11 | D02372A | | | | D05210P | | 9 | | ALL |
| 025 | 24 | | PK | | 6-0 | 32-42-11 | D02372A | | | | D04908P | | 12 | | ALL |
| 026 | 24 | | PK | | 6-0 | 32-42-11 | D02372B | | | | D04908P | | 16 | | ALL |
| 027 | 24 | | PK | | 6-0 | 32-42-11 | D02372B | | | | D04908P | | 14 | | ALL |
| 028 | 24 | | PK | | 6-0 | 32-42-11 | D02372A | | | | D04908P | | 11 | | ALL |
| 029 | 24 | | PK | | 3-9 | 32-42-11 | D02372A | | | | D05230P | | 5 | | ALL |
| 030 | 24 | | PK | | 3-9 | 32-42-11 | D02372A | | | | D05230P | | 6 | | ALL |
| 031 | 24 | | PK | | 3-9 | 32-42-11 | D02372A | | | | D05230P | | 7 | | ALL |
| 032 | 24 | | PK | | 2-10 | 32-42-11 | D02372B | | | | D05066P | | 2 | | ALL |
| 033 | 24 | | PK | | 2-10 | 32-42-11 | D02372B | | | | D05066P | | 3 | | ALL |
| 034 | 24 | | PK | | 2-10 | 32-42-11 | D02372B | | | | D05066P | | 4 | | ALL |
| 037 | 20 | | UA | | 2-1 | 32-42-11 | D02372B | | | | GDX0014 | S.. | 2 | | ALL |
| 038 | 20 | | UA | | 2-1 | 32-42-11 | D02372A | | | | GDX0014 | S.. | 2 | | ALL |
| 039 | 24 | | PK | | 2-10 | 32-42-12 | D02372A | | | | D04656P | | 2 | | ALL |
| 040 | 24 | | PK | | 2-10 | 32-42-12 | D02372A | | | | D04656P | | 3 | | ALL |
| 041 | 24 | | PK | | 5-2 | 32-42-12 | D02372A | | | | D04674P | | 6 | | ALL |
| 042 | 24 | | PK | | 5-2 | 32-42-12 | D02372B | | | | D04674P | | 5 | | ALL |
| 043 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | | | D04656P | | 6 | | ALL |
| 044 | 24 | | PK | | 5-2 | 32-42-12 | D02372B | | | | D04674P | | 4 | | ALL |
| 045 | 24 | | PK | | 5-2 | 32-42-12 | D02372B | | | | D04674P | | 7 | | ALL |
| 046 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | | | D04656P | | 4 | | ALL |
| 047 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | | | D04656P | | 8 | | ALL |
| 048 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | | | D04656P | | 9 | | ALL |
| 049 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | | | D04656P | | 10 | | ALL |
| 050 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | | | D04656P | | 11 | | ALL |
| 051 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | | | D04656P | | 12 | | ALL |
| 052 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | | | D04656P | | 13 | | ALL |
| 053 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | | | D04656P | | 18 | | ALL |
| 054 | 24 | | PK | | 2-11 | 32-42-12 | TB0101G | | 88 | 2 | D04656P | | 19 | | ALL |
| 055 | 24 | | PK | | 2-10 | 32-42-12 | D02372A | | | | D04656P | | 20 | | ALL |
| 056 | 24 | | PK | | 2-11 | 32-42-12 | TB0101G | | 87 | 2 | D04656P | | 21 | | ALL |
| 057 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | | | D04656P | | 23 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W1080
 Page 21
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|---|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1084 | 286T1084 | | | SHELF E-1 INTEGRATION (continued) | | | | | | | | | | | | | | |
| 058 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | C09 | | | | | D04656P | 24 | | | ALL |
| 059 | 24 | | PK | | 2-9 | 32-42-12 | D02372B | | C12 | | | | | TB0101G | 88 | 2 | | ALL |
| 060 | 24 | | PK | | 5-2 | 32-42-12 | D02372B | | C08 | | | | | D04674P | 1 | | | ALL |
| 061 | 24 | | PK | | 5-2 | 32-42-12 | D02372B | | A08 | | | | | D04674P | 2 | | | ALL |
| 062 | 24 | | PK | | 2-9 | 32-42-12 | D02372B | | D04 | | | | | TB0101G | 87 | 2 | | ALL |
| 063 | 24 | | PK | | 2-10 | 32-42-12 | D02372A | | A10 | | | | | D05066P | 5 | | | ALL |
| 064 | 24 | | PK | | 2-10 | 32-42-12 | D02372A | | B10 | | | | | D05066P | 6 | | | ALL |
| 065 | 24 | | PK | | 2-10 | 32-42-12 | D02372A | | B08 | | | | | D05066P | 10 | | | ALL |
| 066 | 24 | | PK | | 2-10 | 32-42-12 | D02372A | | C07 | | | | | D05066P | 11 | | | ALL |
| 067 | 24 | | PK | | 6-2 | 32-42-11 | TB0101G | | 97 | 2 | | | | D04908P | 17 | | | ALL |
| 068 | 24 | | PK | | 3-8 | 32-42-12 | D02372B | | B08 | | | | | D05350P | 13 | | | ALL |
| 069 | 24 | | PK | | 2-11 | 32-42-12 | TB0101G | | 87 | 2 | | | | D05066P | 13 | | | ALL |
| 070 | 24 | | PK | | 3-8 | 32-42-12 | D02372B | | A09 | | | | | D05350P | 11 | | | ALL |
| 071 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | A10 | | | | | D05066P | 12 | | | ALL |
| 072 | 24 | | PK | | 6-2 | 32-42-11 | TB0101H | | 95 | 2 | | | | D04908P | 13 | | | ALL |
| 073 | 20 | | UA | | 2-1 | 32-42-12 | D02372A | | | | | | FE | GDY0014 | S.. | 2 | | ALL |
| 074 | 22 | | PA | | 2-8 | 32-44-11 | D02372A | | D15 | | | | | D05210P | 1 | | | ALL |
| 075 | 24 | | PK | | 5-4 | 32-42-11 | TB0101H | | 95 | 2 | | | | D04674P | 3 | | | ALL |
| 076 | 22 | | PA | | 2-1 | 32-42-11 | D02372A | | C15 | | | | | GDY0014 | D.. | 2 | | ALL |
| 077 | 24 | | PK | | 2-9 | 32-42-12 | D02372B | | C03 | | | | | TB0101G | 88 | 2 | | ALL |
| 078 | 24 | | PK | | 6-2 | 32-42-11 | D04908P | | 4 | | | | | TB0101H | 95 | 2 | | ALL |
| 079 | 24 | | PK | | 6-2 | 32-42-11 | TB0101G | | 94 | 2 | | | | D04908P | 15 | | | ALL |
| 080 | 24 | | PK | | 3-0 | 32-42-11 | D04656P | | 28 | | | | | TB0101H | 95 | 2 | | ALL |
| 081 | 24 | | PK | | 2-8 | 32-42-11 | TB0101H | | 95 | 2 | | | | D02372B | A11 | | | ALL |
| 082 | 24 | | PK | | 2-10 | 32-42-12 | D02372B | | B09 | | | | | D04656P | 5 | | | ALL |
| 083 | 22 | | PA | | 2-8 | 32-41-11 | D02372B | | D15 | | | | | D05210P | 2 | | | ALL |
| 084 | 24 | | PK | | 2-7 | 32-42-11 | D02372A | | C05 | | | | | TB0101G | 94 | 2 | | ALL |
| 085 | 20 | | UA | | 2-1 | 32-42-11 | D02372B | | | | | | | GDY0014 | S.. | 2 | | ALL |
| 086 | 20 | | UA | | 2-1 | 32-42-11 | D02372A | | | | | | | GDY0014 | S.. | 2 | | ALL |
| 087 | 24 | | PK | | 2-10 | 32-42-12 | D04656P | | 29 | | | | | D02372B | C10 | | | ALL |
| 097 | 24 | | PK | | 2-10 | 32-42-11 | TB0101G | | 93 | 2 | | | | D05210P | 12 | | | ALL |
| 098 | 24 | | PK | | 2-10 | 32-42-11 | TB0101G | | 89 | 2 | | | | D05210P | 10 | | | ALL |
| 099 | 24 | | PK | | 2-8 | 32-42-11 | TB0101G | | 97 | 2 | | | | D02372B | C01 | | | ALL |
| 100 | 24 | | PK | | 2-7 | 32-42-11 | TB0101G | | 93 | 2 | | | | D02372A | C03 | | | ALL |
| 101 | 24 | | PK | | 2-9 | 32-42-11 | TB0101G | | 89 | 2 | | | | D02372A | C01 | | | ALL |
| 201B | 22 | | PR | A | 5-5 | 32-42-11 | D02372B | | A06 | | | | | D04930P | 17 | | | ALL |
| 201R | 22 | | PR | A | 0-0 | 32-42-11 | D02372B | | A05 | | | | | D04930P | 13 | | | ALL |
| 201Z | | | | A | 0-0 | 32-42-11 | D02372B | | | | | | | D04930P | 20 | | | ALL |
| 202B | 22 | | PR | B | 5-5 | 32-42-11 | D02372B | | A13 | | | | | D04930P | 19 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 22

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | | |
|------------------------|-----------------|----|------|---|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|----|----|-----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W1084 | 286T1084 | | | SHELF E1-1 INTEGRATION (continued) | | | | | | | | | | | | | | | |
| 202R | 22 | PR | B | 0-0 | 32-42-11 | D02372B | A12 | | | | | | | | | 18 | | ALL | |
| 202Z | | | B | 0-0 | 32-42-11 | D02372B | | | | | FA | | | | | | 21 | | ALL |
| 203B | 22 | PR | C | 3-8 | 32-42-11 | D02372A | B06 | | | | | | | | | | 8 | | ALL |
| 203R | 22 | PR | C | 0-0 | 32-42-11 | D02372A | B05 | | | | | | | | | | 7 | | ALL |
| 203Z | | | C | 0-0 | 32-42-11 | D02372A | | | | | FB | | | | | | 5 | | ALL |
| 204B | 22 | PR | D | 3-8 | 32-42-11 | D02372A | B13 | | | | | | | | | | 10 | | ALL |
| 204R | 22 | PR | D | 0-0 | 32-42-11 | D02372A | B12 | | | | | | | | | | 9 | | ALL |
| 204Z | | | D | 0-0 | 32-42-11 | D02372A | | | | | FB | | | | | | 6 | | ALL |
| 207B | 22 | PR | G | 5-1 | 32-42-11 | D02372B | B06 | | | | | | | | | | 8 | | ALL |
| 207R | 22 | PR | G | 0-0 | 32-42-11 | D02372B | B05 | | | | | | | | | | 7 | | ALL |
| 207Z | | | G | 0-0 | 32-42-11 | D02372B | | | | | FC | | | | | | 6 | | ALL |
| 208B | 22 | PR | H | 5-1 | 32-42-11 | D02372B | B13 | | | | | | | | | | 10 | | ALL |
| 208R | 22 | PR | H | 0-0 | 32-42-11 | D02372B | B12 | | | | | | | | | | 9 | | ALL |
| 208Z | | | H | 0-0 | 32-42-11 | D02372B | | | | | FC | | | | | | 11 | | ALL |
| 209B | 22 | PR | J | 3-8 | 32-42-11 | D02372A | A06 | | | | | | | | | | 17 | | ALL |
| 209R | 22 | PR | J | 0-0 | 32-42-11 | D02372A | A05 | | | | | | | | | | 16 | | ALL |
| 209Z | | | J | 0-0 | 32-42-11 | D02372A | | | | | FD | | | | | | 20 | | ALL |
| 210B | 22 | PR | K | 3-8 | 32-42-11 | D02372A | A13 | | | | | | | | | | 19 | | ALL |
| 210R | 22 | PR | K | 0-0 | 32-42-11 | D02372A | A12 | | | | | | | | | | 18 | | ALL |
| 210Z | | | K | 0-0 | 32-42-11 | D02372A | | | | | FD | | | | | | 21 | | ALL |
| 211B | 24 | PW | L | 2-10 | 32-42-12 | D02372A | D09 | | | | | | | | | | 8 | | ALL |
| 211R | 24 | PW | L | 0-0 | 32-42-12 | D02372A | C09 | | | | | | | | | | 9 | | ALL |
| 211Z | | | L | 0-0 | 32-42-12 | D02372A | | | | | FE | | | | | | 14 | | ALL |
| 212B | 24 | PW | M | 6-0 | 32-42-11 | D02372A | D12 | | | | | | | | | | 2 | | ALL |
| 212R | 24 | PW | M | 0-0 | 32-42-11 | D02372A | D11 | | | | | | | | | | 1 | | ALL |
| 212Z | | | M | 0-0 | 32-42-11 | D02372A | | | | | FG | | | | | | 3 | | ALL |
| 213B | 24 | PW | N | 2-10 | 32-42-11 | D02372B | D14 | | | | | | | | | | 27 | | ALL |
| 213R | 24 | PW | N | 0-0 | 32-42-11 | D02372B | D13 | | | | | | | | | | 26 | | ALL |
| 213Z | | | N | 0-0 | 32-42-11 | D02372B | | | | | FF | | | | | | 25 | | ALL |
| W1085 | 286T1085 | | | E2-2 SHELF,L VOR COAX | | | | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-51-11 | D00329C | = C1 | | | | | | | | | | | | ALL |
| 01CX | | | BR A | 3-11 | 34-51-11 | D00329C | 1 | | | | | | | | | | | | ALL |
| W1086 | 286T1086 | | | MID CABIN PARTITION | | | | | | | | | | | | | | | |
| 001 | 18 | PA | | 10-0 | 33-22-31 | D10174 | 1 | DK | | | | | | | | | 1 | DL | 050-099 |
| 001 | 18 | PA | | 11-0 | 33-22-31 | D10174 | 1 | DK | | | | | | | | | 1 | DL | 150-199, 275-299 |
| 002 | 18 | PA | | 10-0 | 33-22-31 | D10174 | 2 | DK | | | | | | | | | 2 | DL | 050-099 |
| 002 | 18 | PA | | 11-0 | 33-22-31 | D10174 | 2 | DK | | | | | | | | | 2 | DL | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1080
Page 23
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|-------|------|--------|---------|------|------|--------|------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1086 | 286T1086 | | | MID CABIN PARTITION (continued) | | | | | | | | | | | | |
| 003 | 18 | PA | | 10-0 | 33-22-31 | D10174 | | 3 | DK | | D06188P | 3 | DL | | 050-099 | |
| 003 | 18 | PA | | 11-0 | 33-22-31 | D10174 | | 3 | DK | | D06188P | 3 | DL | | 150-199, 275-299 | |
| 004 | 18 | PA | | 10-0 | 33-22-31 | D10174 | | 4 | DK | | D06188P | 4 | DL | | 050-099 | |
| 004 | 18 | PA | | 11-0 | 33-22-31 | D10174 | | 4 | DK | | D06188P | 4 | DL | | 150-199, 275-299 | |
| W1087 | 286T1087 | | | E2-3 SHELF,R VOR COAX | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-51-21 | D00357C | | = C1 | | | D04077P | | = C1 | | ALL | |
| 01CX | | BR | A | 4-0 | 34-51-21 | D00357C | | 1 | | | D04077P | | = A1 | | ALL | |
| W1088 | 286T1088 | | | EMERGENCY EVACUATION MID CABIN PARTITION | | | | | | | | | | | | |
| 002 | 20 | PA | | 13-0 | 25-63-11 | D02972 | | 2 | | | D06026P | 2 | | | 050-099 | |
| 002 | 20 | PA | | 15-0 | 25-63-11 | D02972 | | 2 | | | D06026P | 2 | | | 150-199, 275-299 | |
| 003 | 20 | PA | | 13-0 | 25-63-11 | D02972 | | 3 | | | D06026P | 3 | | | 050-099 | |
| 003 | 20 | PA | | 15-0 | 25-63-11 | D02972 | | 3 | | | D06026P | 3 | | | 150-199, 275-299 | |
| 004 | 20 | PA | | 13-0 | 25-63-11 | D02972 | | 4 | | | D06026P | 4 | | | 050-099 | |
| 004 | 20 | PA | | 15-0 | 25-63-11 | D02972 | | 4 | | | D06026P | 4 | | | 150-199, 275-299 | |
| 005 | 20 | PA | | 13-0 | 25-63-11 | D02972 | | 5 | | | D06026P | 5 | | | 050-099 | |
| 005 | 20 | PA | | 15-0 | 25-63-11 | D02972 | | 5 | | | D06026P | 5 | | | 150-199, 275-299 | |
| W1089 | 286T1089 | | | ATC L (COAX) TO B125,E2-2 SHELF | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-53-11 | D00331C | | = C12 | | | D01331 | | = C1 | | ALL | |
| 01CX | | BR | A | 1-2 | 34-53-11 | D00331C | | 12 | | | D01331 | | = A1 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1080

Page 24 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|-------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1090 | 286T1090 | | | E1-2 INTEGRATION | | | | | | | | | | | |
| 001 | 24 | | PK | | 5-0 | 29-11-32 | D05646P | | 1 | | TB0130G | 170 | 2 | | ALL |
| 003 | 20 | | PA | | 3-2 | 24-11-11 | D05646P | | 3 | | TB0130F | A117 | 2 | | ALL |
| 004 | 18 | | PQ | F | 3-2 | 24-11-11 | D05646P | | 4 | DL | TB0130G | 118 | 2 | | ALL |
| 004Z | | | | F | 0-0 | 24-11-11 | D05646P | | | DED | TB0130G | DED | | | ALL |
| 005 | 22 | | PA | | 6-7 | SPARE | D04751P | | 2 | | D05646P | 7 | | | 150-199, 275-299 |
| 010 | 22 | | PA | | 6-7 | 23-22-11 | D04751P | | 1 | | D05646P | 10 | | | ALL |
| 011 | 22 | | PA | | 3-10 | 29-11-32 | TB0130G | | 170 | 2 | TB0130D | A085 | 2 | | ALL |
| 014 | 24 | | PK | | 3-1 | 27-88-11 | D05646P | | 20 | | TB0130G | 9 | 2 | | ALL |
| 016 | 24 | | PK | | 4-2 | 31-51-41 | D04565P | | 6 | | TB0130F | A143 | 2 | | ALL |
| 018 | 22 | | PA | | 6-7 | SPARE | D04751P | | 3 | | D05646P | 8 | | | 150-199, 275-299 |
| 019 | 22 | | PA | | 6-7 | SPARE | D04751P | | 4 | | D05646P | 9 | | | 150-199, 275-299 |
| 204B | 22 | | PB | D | 3-3 | 27-58-21 | D05646P | | 11 | | D04565P | 1 | | | ALL |
| 204R | 22 | | PB | D | 0-0 | 27-58-21 | D05646P | | 12 | | D04565P | 2 | | | ALL |
| 301B | 24 | | PM | E | 3-3 | 27-58-21 | D05646P | | 13 | | D04565P | 3 | | | ALL |
| 301R | 24 | | PM | E | 0-0 | 27-58-21 | D05646P | | 14 | | D04565P | 4 | | | ALL |
| 301Y | 24 | | PM | E | 0-0 | 27-58-21 | D05646P | | 15 | | D04565P | 5 | | | ALL |
| W1091 | 286T1091 | | | DME L (COAX) TO B125,E2-2 SHELF | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-55-11 | D00333C | | = C12 | | D01333 | = C1 | | | ALL |
| 01CX | | | | BR A | 0-12 | 34-55-11 | D00333C | | 12 | | D01333 | = A1 | | | ALL |
| W1092 | 286T1092 | | | E1-2 INTEGRATION | | | | | | | | | | | |
| 001 | 24 | | PK | | 5-0 | 27-81-11 | D05368P | | 1 | | D02166D | C12 | | | ALL |
| 002 | 24 | | PV | V | 4-6 | 27-88-11 | D02166B | | J15 | | TB0130G | 9 | 2 | | ALL |
| 002Z | | | | V | 0-0 | 27-88-11 | D02166B | | | DED | TB0130G | DED | | | ALL |
| 003 | 24 | | PK | | 2-9 | 27-32-11 | D02166B | | F15 | | D05281P | 2 | | | ALL |
| 004 | 24 | | PK | | 2-9 | 27-32-11 | D02166B | | G13 | | D05281P | 3 | | | ALL |
| 006 | 22 | | PA | | 3-5 | 25-53-21 | D02166D | | B10 | | D05618P | 12 | | | ALL |
| 007 | 22 | | PA | | 3-5 | 25-53-11 | D02166D | | E13 | | D05618P | 2 | | | ALL |
| 008 | 22 | | PQ | Z | 2-0 | 27-88-11 | D02166B | | K15 | | GDX0011 | D.. | 2 | | ALL |
| 008Z | | | | Z | 0-0 | 27-88-11 | D02166B | | | DED | GDX0011 | DED | | | ALL |
| 009 | 24 | | PK | | 3-1 | 24-28-21 | D04058P | | 4 | | TB0130G | 10 | 2 | | ALL |
| 010 | 24 | | PK | | 5-1 | 32-61-14 | D08022P | | 21 | | D10336 | 8 | | | ALL |
| 011 | 20 | | UA | | 1-0 | 21-31-11 | GDX0003 | | S.. | 2 | D00462A | | | FC | ALL |
| 012 | 22 | | PA | | 2-3 | 21-31-11 | GDX0005 | | A.. | 2 | D00462A | D15 | | | ALL |
| 013 | 24 | | PK | | 5-2 | 32-61-14 | D08022P | | 22 | | D10338 | 8 | | | ALL |
| 015 | 24 | | PK | | 3-3 | 21-31-11 | D00462A | | D02 | | D04912P | 7 | | | ALL |
| 016 | 24 | | PK | | 4-7 | 21-31-11 | TB0130G | | 59 | 2 | D04912P | 8 | | | ALL |
| 017 | 24 | | PK | | 3-10 | 21-31-11 | TB0130G | | 59 | 2 | D00462A | B02 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W1090
 Page 1
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | | |
| 018 | 24 | | PK | 3-3 | 21-31-11 | D00462A | A02 | | | | D04912P | 6 | | | ALL | |
| 019 | 22 | | PA | 3-3 | 21-31-11 | D00462A | A15 | | | | D04912P | 19 | | | ALL | |
| 01A | 24 | | PK | 5-3 | 27-32-11 | D02166B | K13 | | | | TB0130D | C190 | 2 | | ALL | |
| 01B | 24 | | PK | 5-8 | 27-32-11 | D05281P | 4 | | | | TB0130D | A190 | 2 | | ALL | |
| 01C | 24 | | PK | 7-10 | 27-32-11 | D05544P | 17 | | | | TB0130D | A190 | 2 | | ALL | |
| 01D | 24 | | PK | 5-3 | 27-32-21 | D02166B | A08 | | | | TB0130D | C053 | 2 | | ALL | |
| 01E | 24 | | PK | 4-11 | 27-32-21 | TB0130D | C053 | 2 | | | TB0130D | C171 | 2 | | ALL | |
| 01F | 24 | | PK | 5-6 | 27-32-21 | D05281P | 14 | | | | TB0130D | A171 | 2 | | ALL | |
| 01G | 24 | | PK | 5-9 | 27-32-21 | D05544P | 4 | | | | TB0130D | A171 | 2 | | ALL | |
| 020 | 24 | | PK | 3-9 | 21-31-11 | TB0130G | 59 | 2 | | | D05544P | 11 | | | ALL | |
| 021 | 24 | | PK | 6-5 | 32-61-14 | D05122P | 8 | | | | TB0130D | C188 | 2 | | ALL | |
| 022 | 24 | | PK | 4-9 | 21-31-11 | TB0130D | A092 | 2 | | | D00462A | B08 | | | ALL | |
| 023 | 24 | | PK | 6-0 | 21-31-11 | TB0130D | C092 | 2 | | | D05368P | 2 | | | ALL | |
| 024 | 24 | | PK | 4-7 | 27-58-11 | TB0130D | A055 | 2 | | | D05368P | 29 | | | ALL | |
| 025 | 24 | | PK | 4-10 | 27-88-11 | TB0130G | 182 | 2 | | | D05368P | 30 | | | ALL | |
| 027 | 24 | | PK | 5-5 | 24-11-11 | TB0130R | A189 | 2 | | | D04058P | 47 | | | ALL | |
| 028 | 22 | | PQ | 2-9 | 78-34-11 | D02166A | E02 | | | | TB0130D | C172 | 2 | | ALL | |
| 028Z | | | | 0-0 | 78-34-11 | D02166A | DED | | | | TB0130D | DED | | | ALL | |
| 029 | 24 | | PV | 2-9 | 78-34-11 | D02166A | H05 | | | | TB0130D | C173 | 2 | | ALL | |
| 029Z | | | | 0-0 | 78-34-11 | D02166A | DED | | | | TB0130D | DED | | | ALL | |
| 031 | 24 | | PK | 5-0 | 27-81-11 | D02166B | C14 | | | | D05368P | 36 | | | ALL | |
| 032 | 24 | | PK | 3-8 | 27-88-11 | D05368P | 4 | | | | D05122P | 35 | | | ALL | |
| 036 | 24 | | PK | 3-8 | 27-88-11 | D05368P | 3 | | | | D05122P | 36 | | | ALL | |
| 037 | 22 | | PA | 2-7 | 21-31-11 | D00462A | B12 | | | | GDX0007 | S.. | 2 | | ALL | |
| 039 | 24 | | PV | 1-11 | 32-61-14 | D02166E | G11 | | | | TB0288D | C001 | 2 | | ALL | |
| 039Z | | | | 0-0 | 32-61-14 | D02166E | DED | | | | TB0288D | DED | | | ALL | |
| 040 | 24 | | PK | 2-11 | 32-61-14 | D02166E | E04 | | | | TB0130F | A060 | 2 | | ALL | |
| 041 | 24 | | PV | 1-11 | 32-61-14 | D02166E | J11 | | | | TB0288D | C002 | 2 | | ALL | |
| 041Z | | | | 0-0 | 32-61-14 | D02166E | DED | | | | TB0288D | DED | | | ALL | |
| 042 | 24 | | PV | 1-11 | 32-61-14 | D02166E | G10 | | | | TB0288D | C004 | 2 | | ALL | |
| 042Z | | | | 0-0 | 32-61-14 | D02166E | DED | | | | TB0288D | DED | | | ALL | |
| 043 | 24 | | PV | 1-11 | 32-61-14 | D02166E | J10 | | | | TB0288D | C003 | 2 | | ALL | |
| 043Z | | | | 0-0 | 32-61-14 | D02166E | DED | | | | TB0288D | DED | | | ALL | |
| 044 | 24 | | PK | 5-0 | 27-88-11 | D02166B | D09 | | | | D05368P | 6 | | | ALL | |
| 045 | 24 | | PK | 5-0 | 27-88-11 | D02166B | H09 | | | | D05368P | 7 | | | ALL | |
| 046 | 24 | | PK | 5-0 | 27-88-11 | D02166B | B09 | | | | D05368P | 8 | | | ALL | |
| 047 | 24 | | PK | 5-0 | 27-88-11 | D02166B | G09 | | | | D05368P | 9 | | | ALL | |
| 048 | 24 | | PK | 5-0 | 27-88-11 | D02166B | C09 | | | | D05368P | 10 | | | ALL | |
| 049 | 24 | | PK | 5-0 | 27-88-11 | D02166B | J09 | | | | D05368P | 11 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|-------------------------------------|-------|------|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1092 | 286T1092 | E1-2 INTEGRATION (continued) | | | | | | | | | | | | | |
| 050 | 18 | PA | | 3-6 | 27-11-11 | D05167P | | 1 | | D05368P | 23 | | | ALL | |
| 051 | 18 | PA | | 3-6 | 27-11-11 | D05167P | | 2 | | D05368P | 21 | | | ALL | |
| 052 | 22 | PQ | GC | 3-1 | 78-36-11 | D05544P | | 19 | | TB0130F | C041 | 2 | | ALL | |
| 052Z | | | GC | 0-0 | 78-36-11 | D05544P | | DED | | TB0130F | DED | | | ALL | |
| 053 | 24 | PK | | 6-5 | 32-61-14 | D05122P | | 9 | | TB0130D | C187 | 2 | | ALL | |
| 054 | 24 | PV | HA | 2-7 | 29-11-32 | D02166B | | H15 | | TB0130G | 170 | 2 | | ALL | |
| 054Z | | | HA | 0-0 | 29-11-32 | D02166B | | DED | | TB0130G | DED | | | ALL | |
| 056 | 24 | PK | | 5-3 | 32-61-14 | D05122P | | 11 | | TB0130G | 76 | 2 | | ALL | |
| 057 | 24 | PK | | 5-5 | 24-11-11 | D04058P | | 22 | | TB0130R | C189 | 2 | | ALL | |
| 058 | 24 | PK | | 2-6 | 32-61-14 | D02166A | | A10 | | TB0130D | C186 | 2 | | ALL | |
| 059 | 24 | PV | KA | 2-4 | 32-61-14 | D02166E | | G09 | | TB0130D | A193 | 2 | | ALL | |
| 059Z | | | KA | 0-0 | 32-61-14 | D02166E | | DED | | TB0130D | DED | | | ALL | |
| 060 | 24 | PK | | 2-6 | 32-61-14 | D02166A | | C08 | | TB0130D | A196 | 2 | | ALL | |
| 061 | 24 | PK | | 2-6 | 32-61-14 | D02166A | | C10 | | TB0130D | C188 | 2 | | ALL | |
| 062 | 24 | PK | | 2-6 | 32-61-14 | D02166A | | A11 | | TB0130D | C187 | 2 | | ALL | |
| 063 | 24 | PV | AV | 3-8 | 32-61-14 | D02166E | | F09 | | TB0130G | 37 | 2 | | ALL | |
| 063Z | | | AV | 0-0 | 32-61-14 | D02166E | | DED | | TB0130G | DED | | | ALL | |
| 066 | 24 | PK | | 2-6 | 32-61-14 | TB0130D | | A183 | 2 | D10512 | 7 | | | ALL | |
| 067 | 24 | PK | | 2-6 | 32-61-14 | D02166A | | C09 | | TB0130D | C185 | 2 | | ALL | |
| 068 | 24 | PK | | 3-0 | 32-61-14 | TB0130D | | A188 | 2 | TB0288D | A001 | 2 | | ALL | |
| 069 | 24 | PK | | 3-11 | 24-27-11 | D04058P | | 52 | | TB0130G | 33 | 2 | | ALL | |
| 070 | 24 | PK | | 2-10 | 24-27-11 | D00248A | | D07 | | TB0130G | 33 | 2 | | ALL | |
| 071 | 20 | PA | | 3-5 | 32-61-14 | D10336 | | 2 | | GDX0005 | D.. | 2 | | ALL | |
| 072 | 20 | PA | | 3-6 | 32-61-14 | D10338 | | 2 | | GDX0005 | D.. | 2 | | ALL | |
| 073 | 24 | PK | | 2-6 | 32-61-14 | D10336 | | 4 | | TB0130F | A181 | 2 | | ALL | |
| 074 | 24 | PK | | 2-7 | 32-61-14 | D10338 | | 4 | | TB0130F | C181 | 2 | | ALL | |
| 083 | 24 | PK | | 3-1 | 33-22-11 | D02166D | | C07 | | D05130P | 5 | | | ALL | |
| 084 | 24 | PK | | 3-1 | 33-22-11 | D02166D | | H06 | | D05130P | 6 | | | ALL | |
| 085 | 24 | PK | | 3-1 | 33-22-11 | D02166D | | J10 | | D05130P | 3 | | | ALL | |
| 086 | 24 | PK | | 3-1 | 33-22-11 | D02166D | | F10 | | D05130P | 4 | | | ALL | |
| 087 | 24 | PV | HO | 3-7 | 33-24-11 | D02166E | | F15 | | TB0130F | A135 | 2 | | ALL | |
| 087Z | | | HO | 0-0 | 33-24-11 | D02166E | | DED | | TB0130F | DED | | | ALL | |
| 088 | 22 | PA | | 2-5 | 33-37-21 | D02166D | | C09 | | TB0130D | C194 | 2 | | ALL | |
| 089 | 22 | PA | | 2-5 | 33-37-21 | D02166D | | E10 | | TB0130D | C195 | 2 | | ALL | |
| 090 | 22 | PA | | 5-0 | 33-42-11 | D02166A | | F08 | | D04676P | 53 | | | ALL | |
| 091 | 24 | PK | | 2-10 | 24-11-11 | D04058P | | 32 | | TB0130G | 6 | 2 | | ALL | |
| 093 | 22 | PA | | 1-9 | 24-11-11 | GDX0005 | | D.. | 2 | D00248B | D15 | | | ALL | |
| 094 | 24 | PK | | 4-2 | 24-11-11 | TB0130R | | C189 | 2 | D00248B | D08 | | | ALL | |
| 096 | 24 | PK | | 3-5 | 24-11-11 | D04058P | | 24 | | D00248A | A02 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 3

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | | | |
| 097 | 24 | | PK | 3-5 | 24-11-11 | D04058P | | 25 | | | | | D00248A | C04 | | | ALL |
| 098 | 22 | | PA | 2-10 | 24-11-11 | TB0130G | | 118 | 2 | | | | D00248A | D02 | | | ALL |
| 099 | 18 | | PA | 3-1 | 24-11-11 | TB0130G | | 118 | 2 | | | | D04060P | 15 | | | ALL |
| 0AP | 24 | | PK | 6-6 | 27-88-11 | D05544P | | 3 | | | | | TB0130G | 9 | 2 | | ALL |
| 0AQ | 24 | | PK | 5-7 | 27-81-21 | TB0130D | | A166 | 2 | | | | D05544P | 18 | | | ALL |
| 0AR | 24 | | PK | 4-10 | 27-81-21 | TB0130D | | C166 | 2 | | | | D02166B | D14 | | | ALL |
| 0AS | 24 | | PK | 7-0 | 27-81-21 | TB0130D | | A166 | 2 | | | | D05368P | 35 | | | ALL |
| 101 | 24 | | PK | 3-5 | 24-11-11 | D00248A | | C06 | | | | | D04058P | 16 | | | ALL |
| 102 | 22 | | PQ | 2-9 | 24-11-11 | D00248B | HC | A03 | | | | | TB0130F | A117 | 2 | | ALL |
| 102Z | | | | 0-0 | 24-11-11 | D00248B | HC | DED | | | | | TB0130F | DED | | | ALL |
| 103 | 22 | | PA | 0-6 | 24-21-11 | SM00001 | | | S | | | | D00248B | A15 | | | ALL |
| 104 | 22 | | PA | 0-6 | 24-21-11 | SM00002 | | | S | | | | D00248B | B15 | | | ALL |
| 105 | 22 | | PA | 0-6 | 24-21-11 | SM00003 | | | S | | | | D00248B | C15 | | | ALL |
| 106 | 22 | | PA | 3-4 | 24-22-11 | D04058P | | 33 | | | | | D00248B | D02 | | | ALL |
| 107 | 24 | | PK | 3-5 | 24-22-11 | D04058P | | 26 | | | | | D00248A | B05 | | | ALL |
| 108 | 20 | | PA | 3-10 | 24-22-11 | D04058P | | 34 | | | | | TB0130G | 136 | 2 | | ALL |
| 109 | 24 | | PK | 3-5 | 24-22-11 | D04058P | | 27 | | | | | D00248A | C02 | | | ALL |
| 110 | 24 | | PK | 3-5 | 24-22-11 | D04058P | | 28 | | | | | D00248A | A05 | | | ALL |
| 111 | 24 | | PK | 3-5 | 24-22-11 | D04058P | | 36 | | | | | D00248A | D06 | | | ALL |
| 112 | 24 | | PK | 3-5 | 24-22-12 | D04058P | | 37 | | | | | D00248A | D05 | | | ALL |
| 113 | 24 | | PK | 2-8 | 24-22-11 | TB0130G | | 136 | 2 | | | | D00248A | C05 | | | ALL |
| 114 | 24 | | PK | 3-4 | 24-22-11 | D04676P | | 1 | | | | | D00248A | A01 | | | ALL |
| 115 | 22 | | PA | 3-7 | 24-22-11 | D04060P | | 9 | | | | | D00248A | B01 | | | ALL |
| 116 | 20 | | PA | 4-0 | 24-22-11 | D04060P | | 10 | | | | | TB0130G | 136 | 2 | | ALL |
| 117 | 22 | | PA | 3-7 | 24-22-11 | D04060P | | 11 | | | | | D00248A | C01 | | | ALL |
| 118 | 18 | | PA | 3-7 | 24-22-11 | D04060P | | 7 | | | | | SM00004 | | S | | ALL |
| 119 | 22 | | PA | 2-2 | 24-22-11 | GDX0007 | | D.. | 2 | | | | D00248A | A07 | | | ALL |
| 121 | 22 | | PA | 1-7 | 32-09-21 | D02166D | | D12 | | | | | GDX0013 | S.. | 2 | | ALL |
| 126 | 24 | | PK | 5-5 | 32-61-14 | D05122P | | 10 | | | | | TB0130G | 78 | 2 | | ALL |
| 127 | 24 | | PK | 2-6 | 31-31-13 | D02166B | | E13 | | | | | TB0130F | A090 | 2 | | ALL |
| 128 | 24 | | PK | 2-6 | 31-31-13 | D02166B | | J10 | | | | | TB0130F | C090 | 2 | | ALL |
| 129 | 24 | | PK | 2-6 | 31-31-13 | D02166B | | E15 | | | | | TB0130G | 182 | 2 | | ALL |
| 130 | 24 | | PK | 2-6 | 31-31-13 | D02166B | | H13 | | | | | TB0130F | C089 | 2 | | ALL |
| 131 | 24 | | PK | 2-6 | 31-31-13 | D02166B | | E10 | | | | | TB0130F | A088 | 2 | | ALL |
| 132 | 24 | | PK | 2-6 | 31-31-13 | D02166B | | G10 | | | | | TB0130F | C088 | 2 | | ALL |
| 133 | 24 | | PK | 2-6 | 31-31-13 | D02166B | | G15 | | | | | TB0130F | A087 | 2 | | ALL |
| 134 | 24 | | PK | 2-11 | 24-28-21 | D00248A | | B02 | | | | | TB0130G | 10 | 2 | | ALL |
| 135 | 24 | | PK | 2-11 | 24-28-21 | D00248A | | A10 | | | | | TB0130G | 10 | 2 | | ALL |
| 138 | 24 | | PK | 6-5 | 32-61-14 | D05122P | | 7 | | | | | TB0130D | C186 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | | |
| 139 | 24 | | PK | | 6-5 | 32-61-14 | D05122P | | 6 | | | TB0130D | C185 | 2 | | ALL |
| 140 | 24 | | PK | | 6-1 | 32-61-14 | D05122P | | 5 | | | D02166A | F02 | | | ALL |
| 141 | 24 | | PK | | 2-7 | 32-61-14 | D10336 | | 6 | | | TB0130G | 78 | 2 | | ALL |
| 142 | 24 | | PK | | 3-4 | 31-51-42 | D05281P | | 11 | | | TB0288D | A005 | 2 | | ALL |
| 153 | 24 | | PV | I | 4-6 | 32-42-11 | D05554P | | 15 | | | TB0130F | A169 | 2 | | ALL |
| 153Z | | | | I | 0-0 | 32-42-11 | D05554P | | DED | | | TB0130F | DED | | | ALL |
| 162 | 24 | | PK | | 2-9 | 32-61-14 | D10336 | | 7 | | | TB0130H | 74 | 2 | | ALL |
| 164 | 24 | | PK | | 2-11 | 33-16-14 | D04676P | | 13 | | | TB0130G | 11 | 2 | | ALL |
| 165 | 22 | | PQ | HQ | 3-1 | 33-51-21 | D02166D | | F13 | | | D05130P | 2 | | | ALL |
| 165Z | | | | HQ | 0-0 | 33-51-21 | D02166D | | DED | | | D05130P | DED | | | ALL |
| 166 | 22 | | PQ | HR | 3-1 | 33-51-21 | D02166D | | E09 | | | D05130P | 1 | | | ALL |
| 166Z | | | | HR | 0-0 | 33-51-21 | D02166D | | DED | | | D05130P | DED | | | ALL |
| 167 | 24 | | PK | | 2-6 | 78-34-21 | D02166E | | C15 | | | TB0130F | A086 | 2 | | 050-099, 150-199 |
| 167 | 24 | | PK | | 2-6 | 78-34-21 | D02166E | | C15 | | | TB0130F | A083 | 2 | | 275-299 |
| 168 | 22 | | PA | | 2-0 | 78-34-21 | D02166E | | D15 | | | GD0011 | D.. | 2 | | ALL |
| 169 | 22 | | PA | | 2-7 | 78-34-21 | D02166E | | D10 | | | TB0130D | C174 | 2 | | ALL |
| 170 | 24 | | PK | | 2-7 | 78-34-21 | D02166E | | F11 | | | TB0130D | C175 | 2 | | ALL |
| 171 | 24 | | PV | EW | 5-3 | 78-36-11 | D08022P | | 15 | | | D02166A | G04 | | | ALL |
| 171Z | | | | EW | 0-0 | 78-36-11 | D08022P | | DED | | | D02166A | DED | | | ALL |
| 172 | 24 | | PV | EY | 3-1 | 78-36-11 | TB0130F | | C048 | 2 | | D02166A | H03 | | | ALL |
| 172Z | | | | EY | 0-0 | 78-36-11 | TB0130F | | DED | | | D02166A | DED | | | ALL |
| 173 | 22 | | PQ | EZ | 2-1 | 78-36-11 | GD0011 | | D.. | 2 | | D02166A | H04 | | | ALL |
| 173Z | | | | EZ | 0-0 | 78-36-11 | GD0011 | | DED | | | D02166A | DED | | | ALL |
| 174 | 24 | | PV | GA | 3-1 | 78-36-11 | TB0130F | | A048 | 2 | | D02166A | F06 | | | ALL |
| 174Z | | | | GA | 0-0 | 78-36-11 | TB0130F | | DED | | | D02166A | DED | | | ALL |
| 175 | 24 | | PK | | 2-8 | 78-36-21 | TB0130F | | C073 | 2 | | D02166E | A14 | | | ALL |
| 176 | 22 | | PA | | 2-0 | 78-36-21 | GD0011 | | D.. | 2 | | D02166E | B14 | | | ALL |
| 177 | 24 | | PK | | 5-5 | 78-36-21 | D05122P | | 15 | | | D02166E | B13 | | | ALL |
| 178 | 24 | | PK | | 5-5 | 78-36-21 | D05122P | | 14 | | | D02166E | E13 | | | ALL |
| 179 | 22 | | PA | | 1-6 | 32-09-12 | D02166E | | K15 | | | GD0013 | D.. | 2 | | ALL |
| 180 | 24 | | PV | AW | 2-8 | 32-09-12 | D02166E | | E10 | | | TB0130F | A069 | 2 | | ALL |
| 180Z | | | | AW | 0-0 | 32-09-12 | D02166E | | DED | | | TB0130F | DED | | | ALL |
| 181 | 24 | | PK | | 2-9 | 32-61-14 | D10338 | | 6 | | | TB0130G | 76 | 2 | | ALL |
| 182 | 24 | | PV | AY | 2-7 | 32-09-12 | D02166E | | J15 | | | TB0130F | C079 | 2 | | ALL |
| 182Z | | | | AY | 0-0 | 32-09-12 | D02166E | | DED | | | TB0130F | DED | | | ALL |
| 183 | 24 | | PV | AZ | 2-11 | 32-09-12 | D02166E | | F14 | | | TB0130F | A067 | 2 | | ALL |
| 183Z | | | | AZ | 0-0 | 32-09-12 | D02166E | | DED | | | TB0130F | DED | | | ALL |
| 184 | 24 | | PV | BD | 2-11 | 32-09-12 | D02166E | | G15 | | | TB0130F | C067 | 2 | | ALL |
| 184Z | | | | BD | 0-0 | 32-09-12 | D02166E | | DED | | | TB0130F | DED | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1090
Page 5
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|-----|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | | |
| 185 | 22 | | PA | 3-0 | 52-11-12 | D02166E | A03 | | | | | D05130P | 40 | | | ALL |
| 186 | 22 | | PA | 3-0 | 52-11-12 | D02166E | F02 | | | | | D05130P | 41 | | | ALL |
| 187 | 22 | | PA | 3-0 | 52-11-12 | D02166E | E02 | | | | | D05130P | 42 | | | ALL |
| 188 | 24 | | PK | 3-0 | 52-11-12 | D02166E | C03 | | | | | D05130P | 43 | | | ALL |
| 189 | 22 | | PA | 2-0 | 52-11-13 | D02166E | D03 | | | | | GDX0011 | D.. | 2 | | ALL |
| 190 | 24 | | PK | 3-5 | 52-34-12 | D02166D | C03 | | | | | D05618P | 1 | | | ALL |
| 191 | 24 | | PK | 3-5 | 52-34-12 | D02166D | E02 | | | | | D05618P | 5 | | | ALL |
| 192 | 24 | | PK | 3-5 | 52-34-12 | D02166D | F02 | | | | | D05618P | 9 | | | ALL |
| 193 | 24 | | PK | 3-5 | 52-34-12 | D02166D | B03 | | | | | D05618P | 4 | | | ALL |
| 194 | 24 | | PK | 3-5 | 52-34-12 | D02166D | A03 | | | | | D05618P | 8 | | | ALL |
| 195 | 24 | | PK | 3-5 | 52-34-12 | D02166D | G06 | | | | | D05618P | 7 | | | ALL |
| 196 | 24 | | PK | 3-5 | 52-34-12 | D02166D | F11 | | | | | D05618P | 6 | | | ALL |
| 197 | 24 | | PK | 6-0 | 52-71-11 | D02166D | J07 | | | | | D05122P | 22 | | | ALL |
| 198 | 24 | | PK | 6-0 | 52-71-11 | D02166D | A07 | | | | | D05122P | 25 | | | ALL |
| 199 | 24 | | PK | 6-0 | 52-71-11 | D02166D | G08 | | | | | D05122P | 26 | | | ALL |
| 200 | 24 | | PK | 4-7 | 74-31-11 | D05368P | 31 | | | | | TB0130D | A053 | 2 | | ALL |
| 201B | 24 | | PW A | 3-10 | 21-31-11 | D00462A | A05 | | | | | TB0130F | A066 | 2 | | ALL |
| 201R | 24 | | PW A | 0-0 | 21-31-11 | D00462A | B06 | | | | | TB0130F | C066 | 2 | | ALL |
| 201Z | | | A | 0-0 | 21-31-11 | TB0130F | A065 | 2 | | | | D00462A | | | FB | ALL |
| 202B | 24 | | PW B | 3-10 | 21-31-11 | D00462A | C05 | | | | | TB0130F | C064 | 2 | | ALL |
| 202R | 24 | | PW B | 0-0 | 21-31-11 | D00462A | D06 | | | | | TB0130F | A064 | 2 | | ALL |
| 202Z | | | B | 0-0 | 21-31-11 | TB0130F | A063 | 2 | | | | D00462A | | | FB | ALL |
| 203B | 24 | | PL E | 2-11 | 21-31-11 | D00462A | D04 | | | | | D05544P | 13 | | | ALL |
| 203R | 24 | | PL E | 0-0 | 21-31-11 | D00462A | D03 | | | | | D05544P | 12 | | | ALL |
| 204B | 24 | | PL F | 2-11 | 21-31-11 | D00462A | C04 | | | | | D05544P | 15 | | | ALL |
| 204R | 24 | | PL F | 0-0 | 21-31-11 | D00462A | C03 | | | | | D05544P | 14 | | | ALL |
| 205B | 24 | | PL G | 3-3 | 21-31-11 | D00462A | A08 | | | | | D04912P | 9 | | | ALL |
| 205R | 24 | | PL G | 0-0 | 21-31-11 | D00462A | A07 | | | | | D04912P | 10 | | | ALL |
| 206B | 24 | | PW D | 4-9 | 21-31-11 | D00462A | C11 | | | | | TB0130F | A095 | 2 | | ALL |
| 206R | 24 | | PW D | 0-0 | 21-31-11 | D00462A | B11 | | | | | TB0130F | C095 | 2 | | ALL |
| 206Z | | | D | 0-0 | 21-31-11 | D00462A | | | | FC | | TB0130F | A097 | 2 | | ALL |
| 207B | 24 | | PW HH | 4-11 | 78-34-11 | D02166A | K04 | | | | | D08020P | 1 | | | ALL |
| 207R | 24 | | PW HH | 0-0 | 78-34-11 | D02166A | J04 | | | | | D08020P | 2 | | | ALL |
| 207Z | | | HH | 0-0 | 78-34-11 | D02166A | DED | | | | | D08020P | DED | | | ALL |
| 208B | 24 | | PL J | 3-3 | 21-31-11 | D00462A | A11 | | | | | D04912P | 11 | | | ALL |
| 208R | 24 | | PL J | 0-0 | 21-31-11 | D00462A | A10 | | | | | D04912P | 12 | | | ALL |
| 209B | 24 | | PL K | 4-4 | 27-88-12 | D02166A | F11 | | | | | D05370P | 19 | | | ALL |
| 209R | 24 | | PL K | 0-0 | 27-88-12 | D02166A | E11 | | | | | D05370P | 20 | | | ALL |
| 210B | 24 | | PL L | 4-4 | 27-88-12 | D02166A | F13 | | | | | D05370P | 25 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 210R | 24 | PL | L | 0-0 | 27-88-12 | D02166A | E13 | | | D05370P | 26 | | | ALL | |
| 211B | 24 | PL | M | 4-4 | 27-88-12 | D02166A | K10 | | | D05370P | 21 | | | ALL | |
| 211R | 24 | PL | M | 0-0 | 27-88-12 | D02166A | J10 | | | D05370P | 22 | | | ALL | |
| 212B | 24 | PL | N | 4-4 | 27-88-12 | D02166A | K12 | | | D05370P | 3 | | | ALL | |
| 212R | 24 | PL | N | 0-0 | 27-88-12 | D02166A | J12 | | | D05370P | 4 | | | ALL | |
| 213B | 24 | PL | P | 4-4 | 27-88-12 | D02166A | H10 | | | D05370P | 9 | | | ALL | |
| 213R | 24 | PL | P | 0-0 | 27-88-12 | D02166A | G10 | | | D05370P | 10 | | | ALL | |
| 214B | 24 | PL | R | 4-4 | 27-88-12 | D02166A | H12 | | | D05370P | 1 | | | ALL | |
| 214R | 24 | PL | R | 0-0 | 27-88-12 | D02166A | G12 | | | D05370P | 2 | | | ALL | |
| 215B | 24 | PL | S | 4-4 | 27-88-12 | D02166A | F10 | | | D05370P | 5 | | | ALL | |
| 215R | 24 | PL | S | 0-0 | 27-88-12 | D02166A | E10 | | | D05370P | 6 | | | ALL | |
| 216B | 24 | PL | T | 4-4 | 27-88-12 | D02166A | F12 | | | D05370P | 7 | | | ALL | |
| 216R | 24 | PL | T | 0-0 | 27-88-12 | D02166A | E12 | | | D05370P | 8 | | | ALL | |
| 217B | 24 | PL | W | 4-4 | 27-88-12 | D02166A | H09 | | | D05370P | 11 | | | ALL | |
| 217R | 24 | PL | W | 0-0 | 27-88-12 | D02166A | G09 | | | D05370P | 12 | | | ALL | |
| 218B | 24 | PL | X | 4-4 | 27-88-12 | D02166A | K11 | | | D05370P | 13 | | | ALL | |
| 218R | 24 | PL | X | 0-0 | 27-88-12 | D02166A | J11 | | | D05370P | 14 | | | ALL | |
| 219B | 24 | PL | Y | 4-4 | 27-88-12 | D02166A | F09 | | | D05370P | 15 | | | ALL | |
| 219R | 24 | PL | Y | 0-0 | 27-88-12 | D02166A | E09 | | | D05370P | 16 | | | ALL | |
| 220B | 24 | PL | AA | 4-4 | 27-88-12 | D02166A | H11 | | | D05370P | 17 | | | ALL | |
| 220R | 24 | PL | AA | 0-0 | 27-88-12 | D02166A | G11 | | | D05370P | 18 | | | ALL | |
| 221B | 24 | PL | AB | 4-7 | 27-88-22 | D02166B | F07 | | | D05434P | 19 | | | ALL | |
| 221R | 24 | PL | AB | 0-0 | 27-88-22 | D02166B | E07 | | | D05434P | 20 | | | ALL | |
| 222B | 24 | PL | AC | 4-7 | 27-88-22 | D02166B | F05 | | | D05434P | 25 | | | ALL | |
| 222R | 24 | PL | AC | 0-0 | 27-88-22 | D02166B | E05 | | | D05434P | 26 | | | ALL | |
| 223B | 24 | PL | AD | 4-7 | 27-88-22 | D02166B | K04 | | | D05434P | 15 | | | ALL | |
| 223R | 24 | PL | AD | 0-0 | 27-88-22 | D02166B | J04 | | | D05434P | 16 | | | ALL | |
| 224B | 24 | PL | AE | 4-7 | 27-88-22 | D02166B | K06 | | | D05434P | 17 | | | ALL | |
| 224R | 24 | PL | AE | 0-0 | 27-88-22 | D02166B | J06 | | | D05434P | 18 | | | ALL | |
| 225B | 24 | PL | AF | 4-7 | 27-88-22 | D02166B | H04 | | | D05434P | 21 | | | ALL | |
| 225R | 24 | PL | AF | 0-0 | 27-88-22 | D02166B | G04 | | | D05434P | 22 | | | ALL | |
| 226B | 24 | PL | AG | 4-7 | 27-88-22 | D02166B | H06 | | | D05434P | 3 | | | ALL | |
| 226R | 24 | PL | AG | 0-0 | 27-88-22 | D02166B | G06 | | | D05434P | 4 | | | ALL | |
| 227B | 24 | PL | AH | 4-7 | 27-88-22 | D02166B | F04 | | | D05434P | 9 | | | ALL | |
| 227R | 24 | PL | AH | 0-0 | 27-88-22 | D02166B | E04 | | | D05434P | 10 | | | ALL | |
| 228B | 24 | PL | AJ | 4-7 | 27-88-22 | D02166B | F06 | | | D05434P | 1 | | | ALL | |
| 228R | 24 | PL | AJ | 0-0 | 27-88-22 | D02166B | E06 | | | D05434P | 2 | | | ALL | |
| 229B | 24 | PL | AK | 4-8 | 27-88-22 | D02166A | K15 | | | D05434P | 5 | | | ALL | |
| 229R | 24 | PL | AK | 0-0 | 27-88-22 | D02166A | J15 | | | D05434P | 6 | | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W1090
Page 7
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 230B | 24 | PL | AL | | 4-7 | 27-88-22 | D02166B | | K05 | | D05434P | | 7 | | ALL |
| 230R | 24 | PL | AL | | 0-0 | 27-88-22 | D02166B | | J05 | | D05434P | | 8 | | ALL |
| 231B | 24 | PL | AM | | 4-8 | 27-88-22 | D02166A | | H15 | | D05434P | | 11 | | ALL |
| 231R | 24 | PL | AM | | 0-0 | 27-88-22 | D02166A | | G15 | | D05434P | | 12 | | ALL |
| 232B | 24 | PL | AN | | 4-7 | 27-88-22 | D02166B | | H05 | | D05434P | | 13 | | ALL |
| 232R | 24 | PL | AN | | 0-0 | 27-88-22 | D02166B | | G05 | | D05434P | | 14 | | ALL |
| 233B | 24 | PL | AP | | 3-8 | 32-61-11 | D02166E | | H03 | | TB0130F | C040 | 2 | | ALL |
| 233R | 24 | PL | AP | | 0-0 | 32-61-11 | D02166E | | G03 | | TB0130F | A040 | 2 | | ALL |
| 234B | 24 | PL | AR | | 3-8 | 32-61-11 | D02166E | | K03 | | TB0130F | C039 | 2 | | ALL |
| 234R | 24 | PL | AR | | 0-0 | 32-61-11 | D02166E | | J03 | | TB0130F | A039 | 2 | | ALL |
| 235B | 24 | PL | AT | | 3-8 | 32-61-11 | D02166E | | H04 | | TB0130F | C038 | 2 | | ALL |
| 235R | 24 | PL | AT | | 0-0 | 32-61-11 | D02166E | | G04 | | TB0130F | A038 | 2 | | ALL |
| 236B | 24 | PW | HK | | 4-11 | 78-34-11 | D02166A | | G05 | | D08020P | | 3 | | ALL |
| 236R | 24 | PW | HK | | 0-0 | 78-34-11 | D02166A | | F05 | | D08020P | | 4 | | ALL |
| 236Z | | | HK | | 0-0 | 78-34-11 | D02166A | | DED | | D08020P | DED | | | ALL |
| 237B | 24 | PL | AX | | 4-11 | 32-61-11 | D02166A | | D03 | | D05554P | | 2 | | ALL |
| 237R | 24 | PL | AX | | 0-0 | 32-61-11 | D02166A | | C03 | | D05554P | | 1 | | ALL |
| 238B | 24 | PL | H | | 4-6 | 27-32-21 | D05281P | | 8 | | TB0130F | C031 | 2 | | ALL |
| 238R | 24 | PL | H | | 0-0 | 27-32-21 | D05281P | | 7 | | TB0130F | A031 | 2 | | ALL |
| 239B | 24 | PL | BA | | 4-11 | 32-61-11 | D02166A | | D02 | | D05554P | | 8 | | ALL |
| 239R | 24 | PL | BA | | 0-0 | 32-61-11 | D02166A | | C02 | | D05554P | | 7 | | ALL |
| 240B | 24 | PL | BB | | 4-11 | 32-61-11 | D02166A | | B03 | | D05554P | | 10 | | ALL |
| 240R | 24 | PL | BB | | 0-0 | 32-61-11 | D02166A | | A03 | | D05554P | | 9 | | ALL |
| 241B | 24 | PL | BC | | 4-3 | 32-61-12 | D02166A | | D05 | | D05544P | | 2 | | ALL |
| 241R | 24 | PL | BC | | 0-0 | 32-61-12 | D02166A | | C05 | | D05544P | | 1 | | ALL |
| 243B | 24 | PL | BE | | 4-3 | 32-61-12 | D02166A | | D04 | | D05544P | | 6 | | ALL |
| 243R | 24 | PL | BE | | 0-0 | 32-61-12 | D02166A | | C04 | | D05544P | | 5 | | ALL |
| 244B | 24 | PL | BF | | 4-3 | 32-61-12 | D02166A | | B05 | | D05544P | | 8 | | ALL |
| 244R | 24 | PL | BF | | 0-0 | 32-61-12 | D02166A | | A05 | | D05544P | | 7 | | ALL |
| 246B | 24 | PL | BG | | 2-6 | 32-61-12 | D02166E | | H05 | | TB0130F | C178 | 2 | | ALL |
| 246R | 24 | PL | BG | | 0-0 | 32-61-12 | D02166E | | G05 | | TB0130F | A178 | 2 | | ALL |
| 247B | 24 | PL | BH | | 2-6 | 32-61-12 | D02166E | | K05 | | TB0130F | C177 | 2 | | ALL |
| 247R | 24 | PL | BH | | 0-0 | 32-61-12 | D02166E | | J05 | | TB0130F | A177 | 2 | | ALL |
| 248B | 24 | PL | BJ | | 2-7 | 32-61-12 | D02166E | | H06 | | TB0130F | C176 | 2 | | ALL |
| 248R | 24 | PL | BJ | | 0-0 | 32-61-12 | D02166E | | G06 | | TB0130F | A176 | 2 | | ALL |
| 250B | 24 | PL | BS | | 3-7 | 32-61-13 | TB0130F | | C140 | 2 | D02166E | | K01 | | ALL |
| 250R | 24 | PL | BS | | 0-0 | 32-61-13 | TB0130F | | A140 | 2 | D02166E | | J01 | | ALL |
| 251B | 24 | PL | BT | | 3-7 | 32-61-13 | TB0130F | | C139 | 2 | D02166E | | H02 | | ALL |
| 251R | 24 | PL | BT | | 0-0 | 32-61-13 | TB0130F | | A139 | 2 | D02166E | | G02 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 252B | 24 | PL | BU | 3-7 | 32-61-13 | TB0130F | C138 | 2 | | D02166E | K02 | | | ALL | |
| 252R | 24 | PL | BU | 0-0 | 32-61-13 | TB0130F | A138 | 2 | | D02166E | J02 | | | ALL | |
| 253B | 24 | PL | BV | 5-0 | 32-61-13 | D02166A | B02 | | | D04676P | 28 | | | ALL | |
| 253R | 24 | PL | BV | 0-0 | 32-61-13 | D02166A | A02 | | | D04676P | 27 | | | ALL | |
| 254B | 24 | PL | BW | 5-0 | 32-61-13 | D02166A | B01 | | | D04676P | 30 | | | ALL | |
| 254R | 24 | PL | BW | 0-0 | 32-61-13 | D02166A | A01 | | | D04676P | 29 | | | ALL | |
| 255B | 24 | PL | BX | 5-0 | 32-61-13 | D02166A | D01 | | | D04676P | 32 | | | ALL | |
| 255R | 24 | PL | BX | 0-0 | 32-61-13 | D02166A | C01 | | | D04676P | 31 | | | ALL | |
| 256B | 24 | PL | BY | 5-0 | 32-61-13 | D02166A | F01 | | | D04676P | 34 | | | ALL | |
| 256R | 24 | PL | BY | 0-0 | 32-61-13 | D02166A | E01 | | | D04676P | 33 | | | ALL | |
| 257B | 24 | PL | BO | 2-9 | 32-09-12 | D02166E | H08 | | | TB0130F | C168 | 2 | | ALL | |
| 257R | 24 | PL | BO | 0-0 | 32-09-12 | D02166E | G08 | | | TB0130F | A168 | 2 | | ALL | |
| 258B | 24 | PL | BP | 2-9 | 32-09-12 | D02166E | K07 | | | TB0130F | C167 | 2 | | ALL | |
| 258R | 24 | PL | BP | 0-0 | 32-09-12 | D02166E | J07 | | | TB0130F | A167 | 2 | | ALL | |
| 259B | 24 | PL | BQ | 4-11 | 32-09-11 | D02166A | B07 | | | D05554P | 6 | | | ALL | |
| 259R | 24 | PL | BQ | 0-0 | 32-09-11 | D02166A | A07 | | | D05554P | 5 | | | ALL | |
| 260B | 24 | PL | BR | 2-9 | 32-61-13 | TB0130F | C165 | 2 | | D02166E | H01 | | | ALL | |
| 260R | 24 | PL | BR | 0-0 | 32-61-13 | TB0130F | A165 | 2 | | D02166E | G01 | | | ALL | |
| 261B | 24 | PL | BN | 4-3 | 32-09-11 | D02166A | D07 | | | D05544P | 10 | | | ALL | |
| 261R | 24 | PL | BN | 0-0 | 32-09-11 | D02166A | C07 | | | D05544P | 9 | | | ALL | |
| 262B | 24 | PL | BL | 2-5 | 32-09-12 | TB0130F | A096 | 2 | | D02166E | H07 | | | ALL | |
| 262R | 24 | PL | BL | 0-0 | 32-09-12 | TB0130F | C096 | 2 | | D02166E | G07 | | | ALL | |
| 263B | 24 | PL | BM | 5-0 | 32-09-11 | D04676P | 11 | | | D02166A | D06 | | | ALL | |
| 263R | 24 | PL | BM | 0-0 | 32-09-11 | D04676P | 10 | | | D02166A | C06 | | | ALL | |
| 264B | 24 | PL | BZ | 3-5 | 24-11-11 | D00248A | A09 | | | D04058P | 12 | | | ALL | |
| 264R | 24 | PL | BZ | 0-0 | 24-11-11 | D00248A | B09 | | | D04058P | 13 | | | ALL | |
| 265B | 24 | PL | CA | 3-5 | 24-11-11 | D00248A | D03 | | | D04058P | 14 | | | ALL | |
| 265R | 24 | PL | CA | 0-0 | 24-11-11 | D00248A | D01 | | | D04058P | 15 | | | ALL | |
| 266B | 24 | PW | CB | 3-5 | 24-11-11 | D00248A | A04 | | | D04058P | 1 | | | ALL | |
| 266R | 24 | PW | CB | 0-0 | 24-11-11 | D00248A | B04 | | | D04058P | 2 | | | ALL | |
| 266Z | | | CB | 0-0 | 24-11-11 | D00248A | C11 | | | D04058P | 3 | | | ALL | |
| 267B | 22 | PR | CD | 3-4 | 24-21-11 | D00248B | A01 | | | D04058P | 5 | | | ALL | |
| 267R | 22 | PR | CD | 0-0 | 24-21-11 | D00248B | B01 | | | D04058P | 6 | | | ALL | |
| 267Z | | | CD | 0-0 | 24-21-11 | D00248B | C01 | | | D04058P | 7 | | | ALL | |
| 268R | 20 | RJ | EM | 3-4 | 77-31-11 | D05368P | 37 | | | D08022P | 1 | | | ALL | |
| 268W | 20 | RJ | EM | 0-0 | 77-31-11 | D05368P | 38 | | | D08022P | 2 | | | ALL | |
| 268Z | | | EM | 0-0 | 77-31-11 | D05368P | 39 | | | D08022P | 3 | | | ALL | |
| 269B | 24 | PL | CF | 2-7 | 78-34-21 | D02166E | D14 | | | TB0130F | A082 | 2 | | ALL | |
| 269R | 24 | PL | CF | 0-0 | 78-34-21 | D02166E | C14 | | | TB0130F | C082 | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W1090
Page 9
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 270B | 24 | PL | CG | 2-7 | 78-34-21 | D02166E | B15 | | | | TB0130F | A081 | 2 | | ALL |
| 270R | 24 | PL | CG | 0-0 | 78-34-21 | D02166E | A15 | | | | TB0130F | C081 | 2 | | ALL |
| 271B | 24 | PW | CH | 5-3 | 78-36-11 | D02166A | K02 | | | | D08022P | 4 | | | ALL |
| 271R | 24 | PW | CH | 0-0 | 78-36-11 | D02166A | J02 | | | | D08022P | 5 | | | ALL |
| 271Z | | | CH | 0-0 | 78-36-11 | D02166A | DED | | | | D08022P | DED | | | ALL |
| 272B | 24 | PW | CI | 5-3 | 78-36-11 | D02166A | K01 | | | | D08022P | 6 | | | ALL |
| 272R | 24 | PW | CI | 0-0 | 78-36-11 | D02166A | J01 | | | | D08022P | 7 | | | ALL |
| 272Z | | | CI | 0-0 | 78-36-11 | D02166A | DED | | | | D08022P | DED | | | ALL |
| 273B | 24 | PW | CJ | 5-3 | 78-36-11 | D02166A | H01 | | | | D08022P | 8 | | | ALL |
| 273R | 24 | PW | CJ | 0-0 | 78-36-11 | D02166A | G01 | | | | D08022P | 9 | | | ALL |
| 273Z | | | CJ | 0-0 | 78-36-11 | D02166A | DED | | | | D08022P | DED | | | ALL |
| 274B | 24 | PW | CK | 5-3 | 78-36-11 | D02166A | H02 | | | | D08022P | 10 | | | ALL |
| 274R | 24 | PW | CK | 0-0 | 78-36-11 | D02166A | G02 | | | | D08022P | 11 | | | ALL |
| 274Z | | | CK | 0-0 | 78-36-11 | D02166A | DED | | | | D08022P | DED | | | ALL |
| 275B | 24 | PL | CL | 2-8 | 78-36-21 | TB0130F | C071 | 2 | | | D02166E | B11 | | | ALL |
| 275R | 24 | PL | CL | 0-0 | 78-36-21 | TB0130F | A071 | 2 | | | D02166E | A11 | | | ALL |
| 276B | 24 | PL | CM | 2-8 | 78-36-21 | TB0130F | C070 | 2 | | | D02166E | B12 | | | ALL |
| 276R | 24 | PL | CM | 0-0 | 78-36-21 | TB0130F | A070 | 2 | | | D02166E | A12 | | | ALL |
| 277B | 24 | PL | CN | 2-7 | 78-36-21 | TB0130F | C080 | 2 | | | D02166E | D11 | | | ALL |
| 277R | 24 | PL | CN | 0-0 | 78-36-21 | TB0130F | A080 | 2 | | | D02166E | C11 | | | ALL |
| 278B | 24 | PL | CO | 2-11 | 78-36-21 | TB0130F | C068 | 2 | | | D02166E | D12 | | | ALL |
| 278R | 24 | PL | CO | 0-0 | 78-36-21 | TB0130F | A068 | 2 | | | D02166E | C12 | | | ALL |
| 279B | 24 | PL | CP | 3-0 | 52-11-13 | D02166E | B01 | | | | D05130P | 11 | | | ALL |
| 279R | 24 | PL | CP | 0-0 | 52-11-13 | D02166E | A01 | | | | D05130P | 10 | | | ALL |
| 280B | 24 | PL | CQ | 3-0 | 52-11-13 | D02166E | D01 | | | | D05130P | 13 | | | ALL |
| 280R | 24 | PL | CQ | 0-0 | 52-11-13 | D02166E | C01 | | | | D05130P | 12 | | | ALL |
| 281B | 24 | PL | CR | 3-0 | 52-11-13 | D02166E | F01 | | | | D05130P | 15 | | | ALL |
| 281R | 24 | PL | CR | 0-0 | 52-11-13 | D02166E | E01 | | | | D05130P | 14 | | | ALL |
| 282B | 24 | PL | CS | 3-0 | 52-11-13 | D02166E | B02 | | | | D05130P | 17 | | | ALL |
| 282R | 24 | PL | CS | 0-0 | 52-11-13 | D02166E | A02 | | | | D05130P | 16 | | | ALL |
| 283B | 24 | PL | CT | 3-3 | 52-34-13 | D02166D | D01 | | | | D05498P | 12 | | | ALL |
| 283R | 24 | PL | CT | 0-0 | 52-34-13 | D02166D | C01 | | | | D05498P | 13 | | | ALL |
| 284B | 24 | PL | CU | 3-3 | 52-34-13 | D02166D | D02 | | | | D05498P | 14 | | | ALL |
| 284R | 24 | PL | CU | 0-0 | 52-34-13 | D02166D | C02 | | | | D05498P | 15 | | | ALL |
| 285B | 24 | PL | CV | 3-3 | 52-34-13 | D02166D | B01 | | | | D05498P | 16 | | | ALL |
| 285R | 24 | PL | CV | 0-0 | 52-34-13 | D02166D | A01 | | | | D05498P | 17 | | | ALL |
| 286B | 24 | PL | CX | 3-3 | 52-34-13 | D02166D | B02 | | | | D05498P | 18 | | | ALL |
| 286R | 24 | PL | CX | 0-0 | 52-34-13 | D02166D | A02 | | | | D05498P | 19 | | | ALL |
| 287B | 24 | PL | CY | 3-3 | 52-34-13 | D02166D | F01 | | | | D05498P | 20 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 287R | 24 | PL | CY | 0-0 | 52-34-13 | D02166D | E01 | | | D05498P | 21 | | | ALL | |
| 288B | 24 | PL | CZ | 3-3 | 52-35-13 | D02166D | B14 | | | D05498P | 2 | | | ALL | |
| 288R | 24 | PL | CZ | 0-0 | 52-35-13 | D02166D | A14 | | | D05498P | 3 | | | ALL | |
| 289B | 24 | PL | DA | 3-3 | 52-35-13 | D02166D | B15 | | | D05498P | 4 | | | ALL | |
| 289R | 24 | PL | DA | 0-0 | 52-35-13 | D02166D | A15 | | | D05498P | 5 | | | ALL | |
| 290B | 24 | PL | DB | 3-3 | 52-35-13 | D02166D | B13 | | | D05498P | 6 | | | ALL | |
| 290R | 24 | PL | DB | 0-0 | 52-35-13 | D02166D | A13 | | | D05498P | 7 | | | ALL | |
| 291B | 24 | PL | DC | 3-3 | 52-35-13 | D02166D | F14 | | | D05498P | 8 | | | ALL | |
| 291R | 24 | PL | DC | 0-0 | 52-35-13 | D02166D | E14 | | | D05498P | 9 | | | ALL | |
| 292B | 24 | PL | DD | 3-3 | 52-35-13 | D02166D | D14 | | | D05498P | 10 | | | 050-099 | |
| 292R | 24 | PL | DD | 0-0 | 52-35-13 | D02166D | C14 | | | D05498P | 11 | | | 050-099 | |
| 293B | 24 | PL | DE | 3-2 | 52-71-11 | D02166D | D04 | | | D05102P | 2 | | | ALL | |
| 293R | 24 | PL | DE | 0-0 | 52-71-11 | D02166D | C04 | | | D05102P | 1 | | | ALL | |
| 294B | 24 | PL | DF | 3-2 | 52-71-11 | D02166D | F04 | | | D05102P | 4 | | | ALL | |
| 294R | 24 | PL | DF | 0-0 | 52-71-11 | D02166D | E04 | | | D05102P | 3 | | | ALL | |
| 295B | 24 | PL | DG | 3-1 | 52-71-11 | D02166D | F03 | | | D05130P | 19 | | | ALL | |
| 295R | 24 | PL | DG | 0-0 | 52-71-11 | D02166D | E03 | | | D05130P | 18 | | | ALL | |
| 296B | 24 | PL | DH | 3-1 | 52-71-11 | D02166D | B04 | | | D05130P | 21 | | | ALL | |
| 296R | 24 | PL | DH | 0-0 | 52-71-11 | D02166D | A04 | | | D05130P | 20 | | | ALL | |
| 297B | 24 | PL | DI | 3-1 | 52-71-11 | D02166D | K03 | | | D05130P | 23 | | | ALL | |
| 297R | 24 | PL | DI | 0-0 | 52-71-11 | D02166D | J03 | | | D05130P | 22 | | | ALL | |
| 298B | 24 | PL | DJ | 3-1 | 52-71-11 | D02166D | H04 | | | D05130P | 25 | | | ALL | |
| 298R | 24 | PL | DJ | 0-0 | 52-71-11 | D02166D | G04 | | | D05130P | 24 | | | ALL | |
| 299B | 24 | PL | DK | 3-1 | 52-71-11 | D02166D | K02 | | | D05130P | 27 | | | ALL | |
| 299R | 24 | PL | DK | 0-0 | 52-71-11 | D02166D | J02 | | | D05130P | 26 | | | ALL | |
| 300 | 24 | PK | | 2-11 | 27-58-11 | D02166B | J13 | | | TB0130D | C055 | 2 | | ALL | |
| 301B | 18 | PC | CC | 3-4 | 24-21-11 | D00248C | 2 | | | D04060P | 1 | | | ALL | |
| 301R | 18 | PC | CC | 0-0 | 24-21-11 | D00248C | 3 | | | D04060P | 2 | | | ALL | |
| 301Y | 18 | PC | CC | 0-0 | 24-21-11 | D00248C | 4 | | | D04060P | 3 | | | ALL | |
| 303B | 18 | PC | KI | 3-6 | 24-21-11 | SM00001 | | S | | D04060P | 4 | | | ALL | |
| 303R | 18 | PC | KI | 0-0 | 24-21-11 | SM00002 | | S | | D04060P | 5 | | | ALL | |
| 303Y | 18 | PC | KI | 0-0 | 24-21-11 | SM00003 | | S | | D04060P | 6 | | | ALL | |
| 401B | 22 | PT | C | 3-3 | 21-31-11 | D00462A | D01 | | | D04912P | 1 | | | ALL | |
| 401G | 22 | PT | C | 0-0 | 21-31-11 | D00462A | C01 | | | D04912P | 2 | | | ALL | |
| 401R | 22 | PT | C | 0-0 | 21-31-11 | D00462A | B01 | | | D04912P | 3 | | | ALL | |
| 401Y | 22 | PT | C | 0-0 | 21-31-11 | D00462A | A01 | | | D04912P | 4 | | | ALL | |
| 401Z | | | C | 0-0 | 21-31-11 | D04912P | 5 | | | D00462A | | | FC | ALL | |
| 402B | 24 | PN | CE | 3-4 | 24-21-11 | D00248B | A13 | | | D04058P | 8 | | | ALL | |
| 402G | 24 | PN | CE | 0-0 | 24-21-11 | D00248B | D13 | | | D04058P | 11 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 402R | 24 | PN | CE | 0-0 | 24-21-11 | D00248B | B13 | | | D04058P | 9 | | | ALL | |
| 402Y | 24 | PN | CE | 0-0 | 24-21-11 | D00248B | C13 | | | D04058P | 10 | | | ALL | |
| 403B | 24 | PN | EH | 3-4 | 24-23-11 | D04058P | 18 | | | D00248B | A11 | | | ALL | |
| 403G | 24 | PN | EH | 0-0 | 24-23-11 | D04058P | 19 | | | D00248B | B11 | | | ALL | |
| 403R | 24 | PN | EH | 0-0 | 24-23-11 | D04058P | 20 | | | D00248B | C11 | | | ALL | |
| 403Y | 24 | PN | EH | 0-0 | 24-23-11 | D04058P | 21 | | | D00248B | D11 | | | ALL | |
| 404B | 24 | PN | EI | 3-4 | 24-23-11 | D04058P | 38 | | | D00248B | A12 | | | ALL | |
| 404G | 24 | PN | EI | 0-0 | 24-23-11 | D04058P | 39 | | | D00248B | B12 | | | ALL | |
| 404R | 24 | PN | EI | 0-0 | 24-23-11 | D04058P | 40 | | | D00248B | C12 | | | ALL | |
| 404Y | 24 | PN | EI | 0-0 | 24-23-11 | D04058P | 41 | | | D00248B | D12 | | | ALL | |
| 405B | 24 | PN | EL | 3-4 | 24-23-11 | D04058P | 42 | | | D00248B | A10 | | | ALL | |
| 405G | 24 | PN | EL | 0-0 | 24-23-11 | D04058P | 43 | | | D00248B | B10 | | | ALL | |
| 405R | 24 | PN | EL | 0-0 | 24-23-11 | D04058P | 44 | | | D00248B | C10 | | | ALL | |
| 405Y | 24 | PN | EL | 0-0 | 24-23-11 | D04058P | 45 | | | D00248B | D10 | | | ALL | |
| 501 | 24 | PK | | 6-0 | 52-71-11 | D02166D | J08 | | | D05122P | 23 | | | ALL | |
| 502 | 24 | PK | | 2-9 | 52-71-11 | D02166D | J11 | | | D05496P | 6 | | | ALL | |
| 503 | 22 | PA | | 2-0 | 52-71-11 | D02166D | K11 | | | GDX0011 | D.. | 2 | | ALL | |
| 504 | 22 | PA | | 4-11 | 52-71-14 | D02166D | K10 | | | D04676P | 41 | | | ALL | |
| 506 | 24 | PK | | 6-0 | 52-71-12 | D02166D | J01 | | | D05122P | 27 | | | 050-099 | |
| 506 | 24 | PK | | 6-0 | 52-71-12 | D02166D | G01 | | | D05122P | 27 | | | 150-199, 275-299 | |
| 507 | 22 | PA | | 2-0 | 52-34-13 | D02166D | D03 | | | GDX0011 | D.. | 2 | | ALL | |
| 508 | 24 | PK | | 3-5 | 52-35-12 | D02166D | C15 | | | D05618P | 15 | | | ALL | |
| 509 | 24 | PK | | 3-5 | 52-35-12 | D02166D | D15 | | | D05618P | 19 | | | ALL | |
| 510 | 24 | PK | | 3-5 | 52-35-12 | D02166D | F15 | | | D05618P | 14 | | | ALL | |
| 511 | 24 | PK | | 3-5 | 52-35-12 | D02166D | E15 | | | D05618P | 18 | | | ALL | |
| 512 | 24 | PK | | 3-5 | 52-35-12 | D02166D | G15 | | | D05618P | 17 | | | ALL | |
| 513 | 24 | PK | | 3-5 | 52-35-12 | D02166D | K09 | | | D05618P | 16 | | | ALL | |
| 514 | 24 | PK | | 1-5 | 32-61-14 | D10338 | 3 | | | D02166E | F05 | | | ALL | |
| 515 | 24 | PK | | 2-9 | 32-61-14 | D10338 | 7 | | | TB0130H | 74 | 2 | | ALL | |
| 517 | 24 | PK | | 2-9 | 32-61-14 | D02166A | H14 | | | TB0130G | 78 | 2 | | ALL | |
| 518 | 24 | PK | | 1-5 | 32-61-14 | D02166E | C09 | | | D10336 | 3 | | | ALL | |
| 519 | 24 | PK | | 2-10 | 32-61-14 | D02166A | E05 | | | TB0130G | 76 | 2 | | ALL | |
| 520 | 24 | PK | | 6-0 | 52-71-13 | D02166D | J13 | | | D05122P | 24 | | | ALL | |
| 521 | 24 | PK | | 6-0 | 52-71-13 | D02166D | G09 | | | D05122P | 33 | | | ALL | |
| 522 | 24 | PK | | 6-0 | 52-71-13 | D02166D | G10 | | | D05122P | 34 | | | ALL | |
| 523 | 24 | PK | | 6-0 | 52-71-14 | D02166D | J14 | | | D05122P | 31 | | | ALL | |
| 524 | 24 | PK | | 6-0 | 52-71-14 | D02166D | G14 | | | D05122P | 32 | | | ALL | |
| 526 | 24 | PK | | 4-0 | 32-61-14 | D08022P | 18 | | | TB0130G | 35 | 2 | | ALL | |
| 527 | 24 | PK | | 6-0 | 52-71-12 | D02166D | G01 | | | D05122P | 29 | | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 527 | 24 | | PK | | 6-0 | 52-71-12 | D02166D | J01 | | | D05122P | 29 | | | 150-199, 275-299 |
| 528 | 24 | | PK | | 6-0 | 52-71-12 | D02166D | A08 | | | D05122P | 28 | | | ALL |
| 529 | 24 | | PK | | 6-0 | 52-71-12 | D02166D | E08 | | | D05122P | 30 | | | ALL |
| 531 | 22 | | PA | | 1-9 | 24-11-11 | D00248B | A08 | | | GDX0005 | S.. | 2 | | ALL |
| 532 | 24 | | PK | | 5-2 | 32-61-14 | D08022P | | | | D10512 | 5 | | | ALL |
| 533 | 24 | | PK | | 5-3 | 32-61-14 | D08022P | | | | D10514 | 5 | | | ALL |
| 534 | 24 | | PK | | 3-0 | 32-61-14 | TB0288D | A002 | 2 | | TB0130D | A187 | 2 | | ALL |
| 535 | 22 | | PA | | 0-6 | 24-22-11 | D00248A | C15 | | | SM00004 | | S | | ALL |
| 536 | 24 | | PK | | 3-5 | 24-22-12 | D04058P | | | | D00248A | A06 | | | ALL |
| 537 | 24 | | PK | | 3-5 | 24-22-12 | D04058P | | | | D00248A | D08 | | | ALL |
| 538 | 20 | | PA | | 6-1 | 24-22-12 | D04058P | | | | TB0130G | 91 | 2 | | ALL |
| 539 | 20 | | PA | | 6-2 | 24-22-12 | D04060P | | | | TB0130G | 91 | 2 | | ALL |
| 540 | 24 | | PK | | 4-5 | 24-22-12 | D00248A | A08 | | | TB0130G | 91 | 2 | | ALL |
| 541 | 18 | | PA | | 3-7 | 24-22-12 | D04060P | | | | SM00005 | | S | | ALL |
| 542 | 22 | | PA | | 3-7 | 24-22-12 | D04060P | | | | D00248A | C07 | | | ALL |
| 543 | 22 | | PA | | 3-7 | 24-22-12 | D04060P | | | | D00248A | C08 | | | ALL |
| 544 | 22 | | PA | | 0-6 | 24-22-12 | SM00005 | | | S | D00248A | D15 | | | ALL |
| 545 | 24 | | PK | | 3-11 | 24-27-11 | D04058P | | | 30 | TB0130G | 33 | 2 | | ALL |
| 546 | 24 | | PK | | 3-5 | 24-22-11 | D04058P | | | 17 | D00248A | D04 | | | ALL |
| 547 | 20 | | PA | | 3-9 | 33-37-21 | D05618P | | | 3 | TB0130D | A194 | 2 | * | ALL |
| 548 | 20 | | PA | | 2-6 | 33-37-21 | TB0130D | A195 | 2 | | TB0130D | A194 | 2 | * | ALL |
| 549 | 24 | | PK | | 2-9 | 27-32-21 | D02166B | K08 | | | D05281P | 13 | | | ALL |
| 551 | 24 | | PK | | 2-9 | 27-32-21 | D02166B | K01 | | | D05281P | 15 | | | ALL |
| 552 | 22 | | PA | | 2-3 | 21-31-11 | D00462A | C12 | | | GDX0005 | D.. | 2 | | ALL |
| 553 | 20 | | UA | | 1-0 | 21-31-11 | D00462A | | | | GDX0003 | S.. | 2 | | ALL |
| 555 | 24 | | PK | | 2-11 | 32-09-13 | TB0130F | A058 | 2 | | D02166E | J14 | | | ALL |
| 556 | 24 | | PK | | 3-0 | 32-61-14 | TB0288D | A003 | 2 | | TB0130D | A186 | 2 | | ALL |
| 557 | 24 | | PK | | 5-1 | 32-09-13 | D05368P | | | 13 | D02166A | H08 | | | ALL |
| 559 | 24 | | PK | | 4-5 | 32-61-14 | D05122P | | | 2 | TB0130G | 35 | 2 | | ALL |
| 560 | 24 | | PK | | 3-10 | 32-61-14 | D02166A | | | D08 | TB0130G | 35 | 2 | | ALL |
| 561 | 24 | | PV | ES | 5-1 | 78-34-11 | D02166A | | | J05 | D05368P | 28 | | | ALL |
| 561Z | | | | ES | 0-0 | 78-34-11 | D02166A | | | DED | D05368P | DED | | | ALL |
| 562 | 22 | | PQ | ET | 2-1 | 78-34-11 | D02166A | | | K05 | GDX0011 | D.. | 2 | | ALL |
| 562Z | | | | ET | 0-0 | 78-34-11 | D02166A | | | DED | GDX0011 | DED | | | ALL |
| 563 | 22 | | PQ | EU | 4-8 | 78-34-11 | TB0130D | | | A172 | D05368P | 24 | | | ALL |
| 563Z | | | | EU | 0-0 | 78-34-11 | TB0130D | | | DED | D05368P | DED | | | ALL |
| 564 | 24 | | PV | EV | 4-8 | 78-34-11 | TB0130D | | | A173 | D05368P | 5 | | | ALL |
| 564Z | | | | EV | 0-0 | 78-34-11 | TB0130D | | | DED | D05368P | DED | | | ALL |
| 565 | 24 | | PK | | 0-7 | 21-31-11 | D00462A | | | D10 | D00462A | D11 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1090
Page 13
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | | |
| 566 | 22 | PQ | O | 1-8 | 32-09-11 | D02166A | D15 | | | | GDX0013 | D.. | 2 | | ALL | |
| 566Z | | | O | 0-0 | 32-09-11 | D02166A | DED | | | | GDX0013 | DED | | | ALL | |
| 567 | 24 | PV | Q | 5-0 | 32-09-11 | D02166A | A15 | | | | D04676P | 23 | | | ALL | |
| 567Z | | | Q | 0-0 | 32-09-11 | D02166A | DED | | | | D04676P | DED | | | ALL | |
| 568 | 24 | PV | U | 3-10 | 32-09-11 | TB0130G | 32 | 2 | | | D04676P | 24 | | | ALL | |
| 568Z | | | U | 0-0 | 32-09-11 | TB0130G | DED | | | | D04676P | DED | | | ALL | |
| 569 | 24 | PK | | 5-0 | 32-09-11 | D02166A | A14 | | | | D04676P | 25 | | | ALL | |
| 570 | 24 | PK | | 3-8 | 32-09-21 | D02166D | A12 | | | | TB0130F | A141 | 2 | | ALL | |
| 571 | 20 | PA | | 3-9 | 33-37-11 | D05618P | 10 | | | | TB0130D | A197 | 2 | | ALL | |
| 572 | 22 | PA | | 2-5 | 33-37-11 | D02166D | D13 | | | | TB0130D | C197 | 2 | | ALL | |
| 574 | 22 | PA | | 2-5 | 32-09-21 | D02166D | B12 | | | | GDX0009 | D.. | 2 | | ALL | |
| 575 | 24 | PK | | 2-6 | 32-42-11 | TB0130D | C196 | 2 | | | TB0130D | C191 | 2 | | ALL | |
| 576 | 24 | PK | | 5-2 | 32-42-11 | TB0130D | A191 | 2 | | | D05554P | 11 | | | ALL | |
| 578 | 24 | PK | | 2-6 | 32-42-11 | TB0130D | C193 | 2 | | | TB0130D | C192 | 2 | | ALL | |
| 579 | 24 | PK | | 0-7 | 52-34-12 | D02166D | D11 | | | | D02166D | E11 | | | ALL | |
| 580 | 24 | PK | | 0-7 | 52-34-12 | D02166D | J09 | | | | D02166D | C13 | | | ALL | |
| 586 | 20 | PA | | 3-2 | 25-31-21 | D04676P | 54 | | | | D04058P | 48 | | | 050-099 | |
| 586 | 20 | PA | | 3-2 | 25-31-21 | D04676P | 54 | DL | | | D04058P | 48 | DL | | 150-199 | |
| 586 | 18 | PA | | 3-2 | 25-31-21 | D04676P | 54 | DL | | | D04058P | 48 | DL | | 275-299 | |
| 587 | 24 | PK | | 5-0 | 32-09-11 | D04676P | 48 | | | | D02166A | C14 | | | ALL | |
| 588 | 24 | PK | | 5-0 | 32-09-11 | D04676P | 47 | | | | D02166A | J13 | | | ALL | |
| 589 | 24 | PV | FA | 5-0 | 32-09-11 | D04676P | 42 | | | | D02166A | H06 | | | ALL | |
| 589Z | | | FA | 0-0 | 32-09-11 | D04676P | DED | | | | D02166A | DED | | | ALL | |
| 590 | 24 | PV | FB | 2-5 | 32-09-12 | TB0130F | C097 | 2 | | | D02166E | J06 | | | ALL | |
| 590Z | | | FB | 0-0 | 32-09-12 | TB0130F | DED | | | | D02166E | DED | | | ALL | |
| 591 | 22 | PA | | 4-11 | 52-71-11 | D04676P | 38 | | | | D02166D | K15 | | | ALL | |
| 592 | 22 | PA | | 4-11 | 52-71-12 | D04676P | 39 | | | | D02166D | H15 | | | ALL | |
| 593 | 22 | PA | | 4-11 | 52-71-13 | D04676P | 40 | | | | D02166D | J15 | | | ALL | |
| 595 | 24 | PK | | 4-5 | 31-51-41 | D05281P | 12 | | | | TB0130F | A143 | 2 | | ALL | |
| 596 | 24 | PK | | 2-10 | 30-41-11 | D04058P | 23 | | | | TB0130G | 8 | 2 | | ALL | |
| 597 | 24 | PK | | 2-10 | 30-41-11 | D04058P | 31 | | | | TB0130G | 7 | 2 | | ALL | |
| 598 | 24 | PK | | 3-5 | 24-11-11 | D04058P | 53 | | | | D00248A | D10 | | | ALL | |
| 599 | 24 | PK | | 0-7 | 21-31-11 | D00462A | D05 | | | | D00462A | C06 | | | ALL | |
| 601B | 24 | PL | DL | 3-1 | 52-71-11 | D02166D | H03 | | | | D05130P | 29 | | | ALL | |
| 601R | 24 | PL | DL | 0-0 | 52-71-11 | D02166D | G03 | | | | D05130P | 28 | | | ALL | |
| 602B | 24 | PL | DM | 3-1 | 52-71-12 | D02166D | H13 | | | | D05130P | 31 | | | ALL | |
| 602R | 24 | PL | DM | 0-0 | 52-71-12 | D02166D | G13 | | | | D05130P | 30 | | | ALL | |
| 603B | 24 | PL | DN | 3-1 | 52-71-12 | D02166D | B11 | | | | D05130P | 33 | | | ALL | |
| 603R | 24 | PL | DN | 0-0 | 52-71-12 | D02166D | A11 | | | | D05130P | 32 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 604B | 24 | PL | DO | | 3-3 | 52-71-12 | D02166D | H02 | | | D05498P | 37 | | | ALL |
| 604R | 24 | PL | DO | | 0-0 | 52-71-12 | D02166D | G02 | | | D05498P | 36 | | | ALL |
| 605B | 24 | PL | DP | | 3-3 | 52-71-12 | D02166D | D05 | | | D05498P | 39 | | | ALL |
| 605R | 24 | PL | DP | | 0-0 | 52-71-12 | D02166D | C05 | | | D05498P | 38 | | | ALL |
| 606B | 24 | PL | DQ | | 3-3 | 52-71-13 | D02166D | H11 | | | D05498P | 23 | | | ALL |
| 606R | 24 | PL | DQ | | 0-0 | 52-71-13 | D02166D | G11 | | | D05498P | 22 | | | ALL |
| 607B | 24 | PL | DR | | 3-3 | 52-71-13 | D02166D | H12 | | | D05498P | 25 | | | ALL |
| 607R | 24 | PL | DR | | 0-0 | 52-71-13 | D02166D | G12 | | | D05498P | 24 | | | ALL |
| 608B | 24 | PL | DS | | 3-3 | 52-71-12 | D02166D | K12 | | | D05498P | 27 | | | ALL |
| 608R | 24 | PL | DS | | 0-0 | 52-71-12 | D02166D | J12 | | | D05498P | 26 | | | ALL |
| 609B | 24 | PL | DT | | 3-3 | 52-71-13 | D02166D | K04 | | | D05498P | 29 | | | ALL |
| 609R | 24 | PL | DT | | 0-0 | 52-71-13 | D02166D | J04 | | | D05498P | 28 | | | ALL |
| 610B | 24 | PL | DU | | 3-3 | 52-71-13 | D02166D | H05 | | | D05498P | 31 | | | ALL |
| 610R | 24 | PL | DU | | 0-0 | 52-71-13 | D02166D | G05 | | | D05498P | 30 | | | ALL |
| 611B | 24 | PL | DV | | 3-3 | 52-71-12 | D02166D | B05 | | | D05498P | 33 | | | ALL |
| 611R | 24 | PL | DV | | 0-0 | 52-71-12 | D02166D | A05 | | | D05498P | 32 | | | ALL |
| 612B | 24 | PL | DW | | 3-3 | 52-71-13 | D02166D | K05 | | | D05498P | 35 | | | ALL |
| 612R | 24 | PL | DW | | 0-0 | 52-71-13 | D02166D | J05 | | | D05498P | 34 | | | ALL |
| 613B | 24 | PL | DX | | 2-9 | 52-71-14 | D02166D | F05 | | | D05496P | 2 | | | ALL |
| 613R | 24 | PL | DX | | 0-0 | 52-71-14 | D02166D | E05 | | | D05496P | 1 | | | ALL |
| 614B | 24 | PL | DY | | 2-9 | 52-71-14 | D02166D | B06 | | | D05496P | 4 | | | ALL |
| 614R | 24 | PL | DY | | 0-0 | 52-71-14 | D02166D | A06 | | | D05496P | 3 | | | ALL |
| 615B | 24 | PL | DZ | | 3-2 | 52-71-11 | D02166D | F06 | | | D05102P | 6 | | | ALL |
| 615R | 24 | PL | DZ | | 0-0 | 52-71-11 | D02166D | E06 | | | D05102P | 5 | | | ALL |
| 616B | 24 | PL | EA | | 3-1 | 52-71-11 | D02166D | D06 | | | D05130P | 35 | | | ALL |
| 616R | 24 | PL | EA | | 0-0 | 52-71-11 | D02166D | C06 | | | D05130P | 34 | | | ALL |
| 617B | 24 | PL | EB | | 3-1 | 52-71-11 | D02166D | H07 | | | D05130P | 37 | | | ALL |
| 617R | 24 | PL | EB | | 0-0 | 52-71-11 | D02166D | G07 | | | D05130P | 36 | | | ALL |
| 618B | 24 | PL | EC | | 3-1 | 52-71-11 | D02166D | K06 | | | D05130P | 39 | | | ALL |
| 618R | 24 | PL | EC | | 0-0 | 52-71-11 | D02166D | J06 | | | D05130P | 38 | | | ALL |
| 620B | 24 | PW | EQ | | 3-2 | 77-31-11 | TB0130Y | C043 | BJ | | D05370P | 38 | | | ALL |
| 620R | 24 | PW | EQ | | 0-0 | 77-31-11 | TB0130Y | A043 | BJ | | D05370P | 37 | | | ALL |
| 620Z | | | EQ | | 0-0 | 77-31-11 | GDY0008 | S.. | 2 | | D05370P | 39 | | | 050-099, 150-199, 275-276 277-299 |
| 620Z | | | EQ | | 0-0 | 77-31-11 | GDY0007 | S.. | 2 | | D05370P | 39 | | | |
| 621B | 24 | PW | EG | | 3-5 | 24-22-12 | D04058P | 49 | | | D00248A | B12 | | | ALL |
| 621R | 24 | PW | EG | | 0-0 | 24-22-12 | D04058P | 50 | | | D00248A | A12 | | | ALL |
| 621Z | | | EG | | 0-0 | 24-22-12 | D04058P | 51 | | | D00248A | B11 | | | ALL |
| 627B | 22 | PB | EO | | 2-11 | 21-31-11 | TB0130F | C105 | 2 | | D00462A | B13 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1090
Page 15
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|----------|---------|---------|-------|------|------|---------|-------|------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 627R | 22 | PB | EO | 0-0 | 21-31-11 | TB0130F | A105 | 2 | | | D00462A | C13 | | | ALL |
| 632B | 24 | PL | KB | 3-0 | 52-71-12 | D02166B | J02 | | | | D05130P | 45 | | | 150-199, 275-299 |
| 632R | 24 | PL | KB | 0-0 | 52-71-12 | D02166B | H02 | | | | D05130P | 44 | | | 150-199, 275-299 |
| 633B | 24 | PL | KC | 3-0 | 52-71-12 | D02166B | G02 | | | | D05130P | 47 | | | 150-199, 275-299 |
| 633R | 24 | PL | KC | 0-0 | 52-71-12 | D02166B | F02 | | | | D05130P | 46 | | | 150-199, 275-299 |
| 648 | 24 | PK | | 3-2 | 24-11-11 | D00248A | A03 | | | | TB0130G | 6 | 2 | | ALL |
| 649 | 24 | PK | | 3-0 | 24-11-11 | D05368P | 17 | | | | TB0130G | 6 | 2 | | ALL |
| 650 | 24 | PK | | 3-5 | 24-11-11 | D05368P | 18 | | | | D00248A | B03 | | | ALL |
| 659B | 24 | PW | A9 | 4-5 | 77-35-11 | D08020P | 14 | | | | TB0130X | C051 | BJ | | ALL |
| 659R | 24 | PW | A9 | 0-0 | 77-35-11 | D08020P | 13 | | | | TB0130X | D051 | BJ | | ALL |
| 659Z | | | A9 | 0-0 | 77-35-11 | D08020P | 10 | | | | GDY0008 | S.. | 2 | | ALL |
| 660B | 24 | PW | B0 | 4-5 | 77-35-11 | D08020P | 16 | | | | TB0130X | A051 | BJ | | ALL |
| 660R | 24 | PW | B0 | 0-0 | 77-35-11 | D08020P | 15 | | | | TB0130X | B051 | BJ | | ALL |
| 660Z | | | B0 | 0-0 | 77-35-11 | D08020P | 11 | | | | GDY0008 | S.. | 2 | | ALL |
| 669 | 24 | PK | | 3-10 | 31-31-22 | D05370P | 27 | | | | TB0130X | D050 | BJ | | ALL |
| 670B | 24 | PW | BI | 2-7 | 73-21-14 | D08020P | 18 | | | | TB0130F | C103 | 2 | | ALL |
| 670R | 24 | PW | BI | 0-0 | 73-21-14 | D08020P | 17 | | | | TB0130F | A103 | 2 | | ALL |
| 670Z | | | BI | 0-0 | 73-21-14 | D08020P | 19 | | | | TB0130F | A104 | 2 | | ALL |
| 671 | 24 | PK | | 6-1 | 32-61-14 | D05122P | 17 | | | | D02166A | F07 | | | ALL |
| 672 | 24 | PK | | 6-1 | 32-61-14 | D05122P | 18 | | | | D02166A | E04 | | | ALL |
| 679 | 22 | PA | | 2-8 | 34-45-13 | D02166E | K13 | | | | TB0130F | C069 | 2 | | 050-099, 153-156, 162-166 |
| 679 | 22 | PA | | 2-5 | 34-45-13 | D02166E | K13 | | | | TB0130F | C093 | 2 | | 150-152, 275-276 |
| 682B | 24 | PW | D2 | 3-9 | 77-12-11 | D08020P | 8 | | | | TB0130Y | C043 | BJ | | 050-099, 162-199, 277-299 |
| 682R | 24 | PW | D2 | 0-0 | 77-12-11 | D08020P | 7 | | | | TB0130Y | A043 | BJ | | 050-099, 162-199, 277-299 |
| 682Z | | | D2 | 0-0 | 77-12-11 | D08020P | 9 | | | | GDY0008 | S.. | 2 | | 050-099, 162-199 |
| 682Z | | | D2 | 0-0 | 77-12-11 | D08020P | 9 | | | | GDY0007 | S.. | 2 | | 277-299 |
| 686 | 22 | PA | | 2-6 | 21-66-11 | D05130P | 48 | | | | D05496P | 5 | | | 050-099, 162-199 |
| 687 | 22 | PA | | 6-5 | 21-66-11 | D04676P | 5 | | | | D05130P | 7 | | | 050-099, 162-199 |
| 688 | 22 | PA | | 6-5 | 21-66-11 | D04676P | 6 | | | | D05130P | 8 | | | 050-099, 162-199 |
| 689 | 22 | PA | | 6-5 | 21-66-11 | D04676P | 7 | | | | D05130P | 9 | | | 050-099, 162-199 |
| 690 | 22 | PA | | 6-4 | 21-66-21 | D04912P | 13 | | | | D05496P | 7 | | | 050-099, 162-199 |
| 691 | 22 | PA | | 6-4 | 21-66-21 | D04912P | 14 | | | | D05496P | 8 | | | 050-099, 162-199 |
| 692 | 22 | PA | | 6-2 | 21-66-21 | D04676P | 4 | | | | D05496P | 9 | | | 050-099, 162-199 |
| 693 | 22 | PA | | 6-4 | 21-66-41 | D05496P | 13 | | | | D04912P | 18 | | | 050-099, 150, 152-199 |
| 694 | 22 | PA | | 6-2 | 21-66-41 | D04676P | 8 | | | | D05496P | 14 | | | 050-099, 150, 152-199 |
| 695 | 22 | PA | | 6-4 | 21-66-41 | D04912P | 21 | | | | D05496P | 15 | | | 050-099, 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1092 | 286T1092 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 700B | 24 | PL | AS | 3-4 | 32-71-11 | D02166A | B08 | | | D08202P | 2 | | | 150-199, 275-299 | |
| 700R | 24 | PL | AS | 0-0 | 32-71-11 | D02166A | A08 | | | D08202P | 1 | | | 150-199, 275-299 | |
| 705 | 24 | PK | | 3-0 | 32-61-14 | TB0130D | A185 | 2 | | TB0288D | A004 | 2 | | ALL | |
| 706 | 24 | PK | | 3-0 | 32-61-14 | TB0130D | C179 | 2 | | TB0130D | A185 | 2 | | ALL | |
| 706B | 24 | PL | AU | 3-4 | 32-71-11 | D02166A | B06 | | | D08202P | 4 | | | 150-199, 275-299 | |
| 706R | 24 | PL | AU | 0-0 | 32-71-11 | D02166A | A06 | | | D08202P | 3 | | | 150-199, 275-299 | |
| 707 | 24 | PV | AO | 3-9 | 32-61-14 | D10512 | | 3 | | TB0130G | 32 | 2 | | ALL | |
| 707Z | | | AO | 0-0 | 32-61-14 | D10512 | DED | | | TB0130G | DED | | | ALL | |
| 708 | 24 | PV | AQ | 2-6 | 32-61-14 | TB0130D | C183 | 2 | | TB0130D | A186 | 2 | | ALL | |
| 708Z | | | AQ | 0-0 | 32-61-14 | TB0130D | DED | | | TB0130D | DED | | | ALL | |
| 709 | 24 | PK | | 3-0 | 32-61-14 | TB0130D | C180 | 2 | | TB0130D | A188 | 2 | | ALL | |
| 710 | 24 | PV | GD | 3-10 | 32-61-14 | D10514 | | 3 | | TB0130G | 32 | 2 | | ALL | |
| 710Z | | | GD | 0-0 | 32-61-14 | D10514 | DED | | | TB0130G | DED | | | ALL | |
| 711 | 24 | PV | GE | 3-0 | 32-61-14 | TB0130D | C184 | 2 | | TB0130D | A187 | 2 | | ALL | |
| 711Z | | | GE | 0-0 | 32-61-14 | TB0130D | DED | | | TB0130D | DED | | | ALL | |
| 715 | 24 | PV | GS | 2-11 | 32-61-14 | D10872 | | 3 | | TB0130H | 74 | 2 | | ALL | |
| 715Z | | | GS | 0-0 | 32-61-14 | D10872 | DED | | | TB0130H | DED | | | ALL | |
| 716 | 24 | PV | GT | 2-11 | 32-61-14 | D10874 | | 3 | | TB0130H | 74 | 2 | | ALL | |
| 716Z | | | GT | 0-0 | 32-61-14 | D10874 | DED | | | TB0130H | DED | | | ALL | |
| 718 | 24 | PK | | 2-6 | 32-61-14 | D02166A | A12 | | | TB0288D | C005 | 2 | | ALL | |
| 719 | 24 | PK | | 3-3 | 32-61-14 | TB0130G | 72 | 2 | | TB0288D | A005 | 2 | | ALL | |
| 720 | 24 | PK | | 3-3 | 32-61-14 | TB0130G | 72 | 2 | | TB0288D | A006 | 2 | | ALL | |
| 721 | 24 | PV | FN | 1-11 | 32-61-14 | D02166E | G12 | | | TB0288D | C006 | 2 | | ALL | |
| 721Z | | | FN | 0-0 | 32-61-14 | D02166E | DED | | | TB0288D | DED | | | ALL | |
| 722 | 24 | PV | FO | 3-10 | 32-09-11 | D02166A | C15 | | | TB0130G | 32 | 2 | | ALL | |
| 722Z | | | FO | 0-0 | 32-09-11 | D02166A | DED | | | TB0130G | DED | | | ALL | |
| 723 | 24 | PK | | 5-1 | 32-61-14 | TB0130F | A057 | 2 | | D05122P | 16 | | | ALL | |
| 732 | 24 | PK | | 6-0 | 52-71-12 | D02166B | K03 | | | D05122P | 12 | | | 150-199, 275-299 | |
| 733 | 24 | PK | | 6-0 | 52-71-12 | D02166B | K02 | | | D05122P | 13 | | | 150-199, 275-299 | |
| 734 | 24 | PK | | 0-7 | 52-71-12 | D02166B | F03 | | | D02166B | G03 | | | 150-199, 275-299 | |
| 735 | 24 | PK | | 0-7 | 52-71-12 | D02166B | H03 | | | D02166B | J03 | | | 150-199, 275-299 | |
| 736 | 18 | PA | | 3-2 | 25-31-31 | D04058P | 46 | DL | | D04676P | 4 | DL | | 277-299 | |
| 737 | 22 | PQ | AI | 2-8 | 29-11-32 | D02166A | A13 | | | TB0130D | C085 | 2 | | ALL | |
| 737Z | | | AI | 0-0 | 29-11-32 | D02166A | DED | | | TB0130D | DED | | | ALL | |
| 738 | 24 | PV | GK | 2-6 | 32-61-14 | D10514 | | 7 | | TB0130D | A184 | 2 | | ALL | |
| 738Z | | | GK | 0-0 | 32-61-14 | D10514 | DED | | | TB0130D | DED | | | ALL | |
| 739 | 24 | PV | GL | 3-10 | 32-61-14 | D04676P | | 2 | | TB0130G | 37 | 2 | | ALL | |
| 739Z | | | GL | 0-0 | 32-61-14 | D04676P | DED | | | TB0130G | DED | | | ALL | |
| 740 | 24 | PV | GM | 5-1 | 32-61-14 | D04676P | | 3 | | D10874 | 5 | | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W1090
Page 17
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|-----|--|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1092 | 286T1092 | | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 740Z | | | GM | 0-0 | 32-61-14 | D04676P | DED | | | D10874 | DED | | | ALL | | |
| 741 | 24 | PV | GN | 5-1 | 32-61-14 | D04676P | 19 | | | D10872 | 5 | | | ALL | | |
| 741Z | | | GN | 0-0 | 32-61-14 | D04676P | DED | | | D10872 | DED | | | ALL | | |
| 742 | 24 | PV | GO | 2-7 | 32-61-14 | D10874 | 2 | | | TB0130D | C183 | 2 | | ALL | | |
| 742Z | | | GO | 0-0 | 32-61-14 | D10874 | DED | | | TB0130D | DED | | | ALL | | |
| 743 | 24 | PV | GP | 2-8 | 32-61-14 | D10874 | 7 | | | TB0130D | A179 | 2 | | ALL | | |
| 743Z | | | GP | 0-0 | 32-61-14 | D10874 | DED | | | TB0130D | DED | | | ALL | | |
| 744 | 24 | PV | GQ | 2-7 | 32-61-14 | D10872 | 2 | | | TB0130D | C184 | 2 | | ALL | | |
| 744Z | | | GQ | 0-0 | 32-61-14 | D10872 | DED | | | TB0130D | DED | | | ALL | | |
| 745 | 24 | PV | GR | 2-9 | 32-61-14 | D10872 | 7 | | | TB0130D | A180 | 2 | | ALL | | |
| 745Z | | | GR | 0-0 | 32-61-14 | D10872 | DED | | | TB0130D | DED | | | ALL | | |
| 746 | 24 | PK | | 2-7 | 32-61-14 | D10512 | 2 | | | TB0130D | C179 | 2 | | ALL | | |
| 747 | 24 | PK | | 2-8 | 32-61-14 | D10514 | 2 | | | TB0130D | C180 | 2 | | ALL | | |
| 751 | 24 | PK | | 4-2 | 31-31-21 | D02166A | B14 | | | TB0130F | C126 | 2 | | ALL | | |
| 752 | 24 | PK | | 4-2 | 31-31-21 | D02166A | C11 | | | TB0130F | A127 | 2 | | ALL | | |
| 755 | 24 | PK | | 0-7 | 32-71-11 | D02166A | J06 | | | D02166A | K06 | | | 150-199, 275-299 | | |
| 756 | 24 | PK | | 0-7 | 32-71-11 | D02166A | J08 | | | D02166A | K08 | | | 150-199, 275-299 | | |
| 757 | 24 | PK | | 4-9 | 32-71-11 | D08022P | 23 | | | TB0130G | 52 | 2 | | 150-199, 275-299 | | |
| 762 | 24 | PK | | 4-0 | 32-71-11 | TB0130D | C049 | 2 | | TB0130D | C192 | 2 | | 150-199, 275-299 | | |
| 763 | 24 | PK | | 4-5 | 32-71-11 | D05554P | 4 | | | TB0130D | A049 | 2 | | 150-199, 275-299 | | |
| 764 | 24 | PK | | 5-1 | 32-71-11 | D05122P | 4 | | | TB0130G | 52 | 2 | | 150-199, 275-299 | | |
| 765 | 24 | PK | | 3-1 | 32-71-11 | D02166A | K09 | | | TB0130G | 52 | 2 | | 150-199, 275-299 | | |
| 779B | 22 | PR | HW | 6-4 | 21-66-21 | D04912P | 16 | | | D05496P | 11 | | | 050-099, 162-199 | | |
| 779R | 22 | PR | HW | 0-0 | 21-66-21 | D04912P | 15 | | | D05496P | 10 | | | 050-099, 162-199 | | |
| 779Z | | | HW | 0-0 | 21-66-21 | D04912P | 17 | | | D05496P | 12 | | | 050-099, 162-199 | | |
| 780B | 22 | PR | HX | 6-4 | 21-66-41 | D04912P | 24 | | | D05496P | 18 | | | 050-099, 150, 152-199 | | |
| 780R | 22 | PR | HX | 0-0 | 21-66-41 | D04912P | 23 | | | D05496P | 17 | | | 050-099, 150, 152-199 | | |
| 780Z | | | HX | 0-0 | 21-66-41 | D04912P | 22 | | | D05496P | 16 | | | 050-099, 150, 152-199 | | |
| 792 | 24 | PV | P2 | 4-0 | 32-61-14 | TB0130G | 137 | 2 | | TB0130D | C196 | 2 | | 050-099, 150-152, 155-199, 275-299 | | |
| 792Z | | | P2 | 0-0 | 32-61-14 | TB0130G | DED | | | TB0130D | DED | | | 050-099, 150-152, 155-199, 275-299 | | |
| 815 | 24 | PK | | 4-0 | 24-11-11 | D04058P | 54 | | | D00248A | D13 | | | ALL | | |
| W1093 | 286T1093 | | | | ATC R (COAX) TO B124,E2-3 SHELF | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-53-21 | D00359C | = C12 | | | D01335 | = C1 | | | ALL | | |
| 01CX | | BR | A | 1-9 | 34-53-21 | D00359C | 12 | | | D01335 | = A1 | | | 050-099, 153-199, 277-299 | | |
| 01CX | | BR | A | 1-6 | 34-53-21 | D00359C | 12 | | | D01335 | = A1 | | | 150-152, 275-276 | | |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 18

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|-------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1095 | 286T1095 | | | DME R (COAX) TO B124,E2-3 SHELF | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-55-21 | D00361C | = C12 | | | D01337 | = C1 | | | ALL |
| 01CX | | BR | | A | 1-6 | 34-55-21 | D00361C | 12 | | | D01337 | = A1 | | | ALL |
| W1096 | 286T1096 | | | E1-2 INTEGRATION | | | | | | | | | | | |
| 101 | 24 | | PK | | 4-3 | 34-22-17 | D04915P | 6 | | | TB0130F | A142 | 2 | | ALL |
| 201B | 24 | | PW | A | 3-7 | 34-43-11 | D04915P | 8 | | | TB0130G | 162 | 2 | | ALL |
| 201R | 24 | | PW | A | 0-0 | 34-43-11 | D04915P | 7 | | | TB0130G | 161 | 2 | | ALL |
| 201Z | | | | A | 0-0 | 34-43-11 | D04915P | 9 | | | GDY0009 | S.. | 2 | | 050-099, 150-199, 275-278 |
| 201Z | | | | A | 0-0 | 34-43-11 | D04915P | 9 | | | GDY0010 | S.. | 2 | | 280-299 |
| 202B | 24 | | PW | B | 3-7 | 22-12-31 | D04915P | 11 | | | TB0130F | C163 | 2 | | ALL |
| 202R | 24 | | PW | B | 0-0 | 22-12-31 | D04915P | 10 | | | TB0130F | A163 | 2 | | ALL |
| 202Z | | | | B | 0-0 | 22-12-31 | D04915P | 12 | | | GDY0009 | S.. | 2 | | 050-099, 150-199, 275-278 |
| 202Z | | | | B | 0-0 | 22-12-31 | D04915P | 12 | | | GDY0010 | S.. | 2 | | 280-299 |
| 203B | 24 | | PW | C | 3-9 | 22-41-11 | D04915P | 14 | | | TB0130F | C158 | 2 | | ALL |
| 203R | 24 | | PW | C | 0-0 | 22-41-11 | D04915P | 13 | | | TB0130F | A158 | 2 | | ALL |
| 203Z | | | | C | 0-0 | 22-41-11 | D04915P | 15 | | | GDY0009 | S.. | 2 | | ALL |
| 207B | 24 | | PW | G | 4-2 | 34-22-18 | D04915P | 21 | | | TB0130F | C144 | 2 | | 050-099 |
| 207B | 24 | | PW | D | 4-2 | 34-22-18 | D04915P | 21 | | | TB0130F | C144 | 2 | | 150-199, 275-299 |
| 207R | 24 | | PW | G | 0-0 | 34-22-18 | D04915P | 20 | | | TB0130F | A144 | 2 | | 050-099 |
| 207R | 24 | | PW | D | 0-0 | 34-22-18 | D04915P | 20 | | | TB0130F | A144 | 2 | | 150-199, 275-299 |
| 207Z | | | | G | 0-0 | 34-22-18 | D04915P | 22 | | | GDY0008 | S.. | 2 | | 050-099 |
| 207Z | | | | D | 0-0 | 34-22-18 | D04915P | 22 | | | GDY0008 | S.. | 2 | | 150-199, 275-299 |
| 208B | 22 | | PR | IH | 4-4 | 32-45-14 | D04915P | 23 | | | TB0130X | A044 | BJ | | 050-099, 150-199 |
| 208R | 22 | | PR | IH | 0-0 | 32-45-14 | D04915P | 24 | | | TB0130X | B044 | BJ | | 050-099, 150-199 |
| 208Z | | | | IH | 0-0 | 32-45-14 | D04915P | 28 | | | TB0130X | A045 | BJ | | 050-099, 150-199 |
| 209B | 22 | | PR | II | 4-4 | 32-45-14 | D04915P | 29 | | | TB0130X | C044 | BJ | | 050-099, 150-199 |
| 209R | 22 | | PR | II | 0-0 | 32-45-14 | D04915P | 30 | | | TB0130X | D044 | BJ | | 050-099, 150-199 |
| 209Z | | | | II | 0-0 | 32-45-14 | D04915P | 31 | | | TB0130X | B045 | BJ | | 050-099, 150-199 |
| 210B | 22 | | PR | IJ | 4-4 | 32-45-14 | D04915P | 32 | | | TB0130X | A046 | BJ | | 050-099, 150-199 |
| 210R | 22 | | PR | IJ | 0-0 | 32-45-14 | D04915P | 33 | | | TB0130X | B046 | BJ | | 050-099, 150-199 |
| 210Z | | | | IJ | 0-0 | 32-45-14 | D04915P | 34 | | | TB0130X | C045 | BJ | | 050-099, 150-199 |
| 211B | 22 | | PR | IK | 4-4 | 32-45-14 | D04915P | 35 | | | TB0130X | C046 | BJ | | 050-099, 150-199 |
| 211R | 22 | | PR | IK | 0-0 | 32-45-14 | D04915P | 36 | | | TB0130X | D046 | BJ | | 050-099, 150-199 |
| 211Z | | | | IK | 0-0 | 32-45-14 | D04915P | 37 | | | TB0130X | D045 | BJ | | 050-099, 150-199 |
| W1098 | 286T1098 | | | E1-2 INTEGRATION | | | | | | | | | | | |
| 002 | 24 | | PK | | 3-0 | 30-41-11 | D02916A | 12 | | | D05344P | | 16 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 19

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|---------|-------|-------------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W1098 | 286T1098 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 003 | 22 | | PA | | 5-0 | 30-41-11 | TB0130G | 7 | 2 | | D05344P | 9 | | | ALL |
| 004 | 24 | | PK | | 3-0 | 30-41-11 | D02916A | 7 | | | D05344P | 7 | | | ALL |
| 005 | 22 | | PA | | 5-0 | 30-41-11 | TB0130G | 8 | 2 | | D05344P | 8 | | | ALL |
| 006 | 24 | | PK | | 3-0 | 30-41-11 | D02916A | 6 | | | D05344P | 6 | | | ALL |
| 007 | 24 | | PK | | 3-0 | 30-41-11 | D02916A | 10 | | | D05344P | 10 | | | ALL |
| 009 | 20 | | PA | | 3-0 | 30-41-11 | D02916A | 2 | | | D05344P | 4 | | | ALL |
| 010 | 20 | | PA | | 3-0 | 30-41-11 | D02916A | 1 | | | D05344P | 5 | | | ALL |
| 011 | 20 | | PA | | 3-0 | 30-41-11 | D02916A | 16 | | | D04292P | 21 | | | ALL |
| 012 | 20 | | PA | | 2-0 | 30-41-11 | D02916A | 3 | | | GDX0007 | A.. | 2 | | ALL |
| 013 | 20 | | PA | | 2-0 | 30-41-11 | D02916A | 4 | | | GDX0007 | D.. | 2 | | ALL |
| 014 | 20 | | PA | | 2-0 | 30-41-11 | D02916A | 5 | | | GDX0007 | D.. | 2 | | ALL |
| 015 | 20 | | PA | | 3-0 | 30-41-11 | D02916A | 11 | | | D04292P | 14 | | | ALL |
| 016 | 20 | | UA | | 2-0 | 30-41-11 | GDX0007 | S.. | 2 | | D02916A | | | FG | ALL |
| 017 | 20 | | UA | | 2-0 | 30-41-11 | GDX0007 | S.. | 2 | | D02916A | | | FH | ALL |
| 018 | 20 | | UA | | 2-0 | 30-41-11 | GDX0007 | S.. | 2 | | D02916A | | | FI | ALL |
| 019 | 12 | | PA | | 3-0 | 30-41-11 | D02916B | 6 | | | D04292P | 8 | | | ALL |
| 020 | 12 | | PA | | 3-0 | 30-41-11 | D02916B | 3 | | | D04292P | 10 | | | ALL |
| 021 | 22 | | PA | | 4-0 | 30-41-11 | D02916A | 9 | | | TB0130G | 7 | 2 | | ALL |
| 022 | 22 | | PA | | 4-0 | 30-41-11 | D02916A | 8 | | | TB0130G | 8 | 2 | | ALL |
| 201B | 24 | | PW | A | 6-0 | 21-31-11 | TB0130F | A095 | 2 | | D05344P | 12 | | | ALL |
| 201R | 24 | | PW | A | 0-0 | 21-31-11 | TB0130F | C095 | 2 | | D05344P | 11 | | | ALL |
| 201Z | | | | A | 0-0 | 21-31-11 | TB0130F | A097 | 2 | | D05344P | 13 | | | ALL |
| 203B | 24 | | PW | L | 3-0 | 30-41-11 | D02916A | 17 | | | D04292P | 23 | | | ALL |
| 203R | 24 | | PW | L | 0-0 | 30-41-11 | D02916A | 18 | | | D04292P | 24 | | | ALL |
| 203Z | | | | L | 0-0 | 30-41-11 | D04292P | 7 | | | D02916A | | | FG | ALL |
| 204B | 24 | | PW | M | 3-0 | 30-41-11 | D02916A | 13 | | | D04292P | 19 | | | ALL |
| 204R | 24 | | PW | M | 0-0 | 30-41-11 | D02916A | 14 | | | D04292P | 20 | | | ALL |
| 204Z | | | | M | 0-0 | 30-41-11 | D04292P | 5 | | | D02916A | | | FH | ALL |
| 205B | 24 | | PW | C | 3-0 | 30-41-11 | D02916A | 19 | | | D04292P | 15 | | | ALL |
| 205R | 24 | | PW | C | 0-0 | 30-41-11 | D02916A | 20 | | | D04292P | 16 | | | ALL |
| 205Z | | | | C | 0-0 | 30-41-11 | D04292P | 3 | | | D02916A | | | FI | ALL |
| 206B | 12 | | PB | I | 3-0 | 30-41-11 | D02916B | 4 | | | D04292P | 4 | | | ALL |
| 206R | 12 | | PB | I | 0-0 | 30-41-11 | D02916B | 5 | | | D04292P | 6 | | | ALL |
| 207B | 12 | | PB | D | 3-0 | 30-41-11 | D02916B | 1 | | | D04292P | 1 | | | ALL |
| 207R | 12 | | PB | D | 0-0 | 30-41-11 | D02916B | 2 | | | D04292P | 2 | | | ALL |
| 214B | 20 | | PB | N | 6-0 | 21-31-11 | TB0130F | C105 | 2 | | D05344P | 14 | | | ALL |
| 214R | 20 | | PB | N | 0-0 | 21-31-11 | TB0130F | A105 | 2 | | D05344P | 15 | | | ALL |
| 900B | 24 | | PW | CA | 3-0 | 34-46-11 | D04292P | 29 | | | TB0130H | 25 | 2 | | 050-099, 150-166, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1090

Page 20

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|--------------------------------------|-------|----------|-------------|------|------|-----------|---------|-------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1098 | 286T1098 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 900R | 24 | PW | CA | | 0-0 | 34-46-11 | D04292P | 28 | | | TB0130H | 23 | 2 | | 050-099, 150-166, 275-299 |
| 900Z | | | CA | | 0-0 | 34-46-11 | D04292P | 30 | | | GDY0007 | S.. | 2 | | 050-099, 150-166, 275-299 |
| W1099 | 286T1099 | | | E2-3 SHELF,R ATC TOP ANT COAX | | | | | | | | | | | |
| 01CO | | | A | | 0-0 | 34-53-13 | D04097P | = C1 | | | D00359A | = C71 | | | ALL |
| 01CX | | JB | A | | 5-0 | 34-53-13 | D04097P | = A1 | | | D00359A | 71 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1090
Page 21 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1100 | 286T1100 | | | E1-2 INTEGRATION | | | | | | | | | | | | | |
| 022 | 24 | | PK | 4-7 | 33-24-11 | D04658P | 24 | | | | | | TB0130F | A135 | 2 | | ALL |
| 048 | 24 | | PK | 3-1 | 78-34-21 | TB0130F | A086 | 2 | | | | | D05638P | 7 | | | 050-099, 150-199 |
| 048 | 24 | | PK | 3-1 | 78-34-21 | TB0130F | A083 | 2 | | | | | D05638P | 7 | | | 275-299 |
| 049 | 22 | | PA | 2-11 | 78-34-21 | TB0130D | A174 | 2 | | | | | D05566P | 14 | | | ALL |
| 050 | 24 | | PK | 3-8 | 78-34-21 | TB0130D | A175 | 2 | | | | | D05638P | 3 | | | ALL |
| 051 | 24 | | PK | 3-10 | 78-36-21 | TB0130F | C073 | 2 | | | | | D05430P | 1 | | | ALL |
| 055 | 22 | | PA | 3-7 | 22-41-11 | D04875P | 2 | | | | | | TB0130F | A149 | 2 | | ALL |
| 056 | 22 | | PA | 4-9 | 34-22-13 | D04875P | 1 | | | | | | TB0130F | A020 | 2 | | ALL |
| 059 | 24 | | PK | 3-10 | 32-09-12 | D05638P | 19 | | | | | | TB0130F | A069 | 2 | | ALL |
| 063 | 24 | | PK | 3-7 | 32-09-12 | D05638P | 17 | | | | | | TB0130F | C079 | 2 | | ALL |
| 064 | 24 | | PK | 4-0 | 32-09-12 | D05638P | 20 | | | | | | TB0130F | A067 | 2 | | ALL |
| 065 | 24 | | PK | 4-0 | 32-09-12 | D05638P | 18 | | | | | | TB0130F | C067 | 2 | | ALL |
| 084 | 24 | | PK | 4-3 | 74-31-21 | D05638P | 24 | | | | | | TB0130D | A054 | 2 | | ALL |
| 085 | 24 | | PK | 2-11 | 74-31-21 | TB0130D | C054 | 2 | | | | | TB0130D | C055 | 2 | | ALL |
| 097 | 24 | | PK | 4-2 | 32-09-13 | TB0130F | A058 | 2 | | | | | D05638P | 6 | | | ALL |
| 104 | 24 | | PK | 4-2 | 32-09-21 | D04658P | 12 | | | | | | TB0130F | A141 | 2 | | ALL |
| 106 | 20 | | PA | 3-9 | 33-43-11 | D05566P | 9 | | | | | | D05638P | 16 | | | 050-099 |
| 106 | 18 | | PA | 3-9 | 33-43-11 | D05566P | 15 | DK | | | | | D05638P | 16 | DL | | 150-199, 275-299 |
| 107 | 24 | | PK | 3-3 | 32-42-11 | TB0130D | A192 | 2 | | | | | TB0130F | A169 | 2 | | ALL |
| 111 | 24 | | PK | 3-1 | 32-09-12 | D04658P | 33 | | | | | | TB0130F | C097 | 2 | | ALL |
| 112 | 24 | | PK | 6-0 | 32-61-14 | D05140P | 8 | | | | | | TB0288D | C001 | 2 | | ALL |
| 113 | 24 | | PK | 3-5 | 32-61-14 | D05140P | 10 | | | | | | TB0130F | A181 | 2 | | 050-099 |
| 113 | 24 | | PK | 5-0 | 32-61-14 | D05140P | 10 | | | | | | TB0130F | A181 | 2 | | 150-199, 275-299 |
| 114 | 24 | | PK | 4-1 | 32-61-14 | D05140P | 5 | | | | | | TB0130F | A060 | 2 | | 050-099 |
| 114 | 24 | | PK | 4-7 | 32-61-14 | D05140P | 5 | | | | | | TB0130F | A060 | 2 | | 150-199, 275-299 |
| 115 | 24 | | PK | 6-0 | 32-61-14 | D05140P | 9 | | | | | | TB0288D | C002 | 2 | | ALL |
| 116 | 24 | | PK | 6-0 | 32-61-14 | D05140P | 6 | | | | | | TB0288D | C004 | 2 | | ALL |
| 117 | 24 | | PK | 6-0 | 32-61-14 | D05140P | 7 | | | | | | TB0288D | C003 | 2 | | ALL |
| 118 | 24 | | PK | 5-0 | 32-61-14 | D05140P | 11 | | | | | | TB0130F | C181 | 2 | | ALL |
| 119 | 24 | | PK | 4-8 | 32-61-14 | D05140P | 2 | | | | | | TB0130G | 37 | 2 | | 050-099 |
| 119 | 24 | | PK | 4-9 | 32-61-14 | D05140P | 2 | | | | | | TB0130G | 37 | 2 | | 150-199, 275-299 |
| 120 | 24 | | PK | 5-0 | 32-61-14 | D05140P | 12 | | | | | | TB0130G | 72 | 2 | | ALL |
| 121 | 24 | | PK | 3-0 | 32-61-14 | D05566P | 20 | | | | | | TB0130H | 74 | 2 | | ALL |
| 122 | 22 | | PQ | BL | 4-8 | 78-36-11 | D05638P | 4 | | | | | TB0130F | C041 | 2 | | ALL |
| 122Z | | | | BL | 0-0 | 78-36-11 | D05638P | DED | | | | | TB0130F | DED | | | ALL |
| 123 | 24 | | PK | 4-3 | 32-61-14 | TB0130F | A057 | 2 | | | | | D05430P | 25 | | | ALL |
| 124 | 24 | | PK | 3-2 | 32-61-14 | D05430P | 21 | | | | | | TB0130D | C193 | 2 | | ALL |
| 125 | 24 | | PV | O | 4-9 | 32-61-14 | D05430P | 22 | | | | | TB0130G | 137 | 2 | | 050-099, 150-152, 155-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1100 | 286T1100 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 125 | 24 | PV | O | 3-2 | 32-61-14 | D05430P | 22 | | | | TB0130D | C196 | 2 | | 153-154 |
| 125Z | | | O | 0-0 | 32-61-14 | D05430P | DED | | | | TB0130D | DED | | | 050-099, 150-156, 162-166, 275-276 |
| 125Z | | | O | 0-0 | 32-61-14 | D05430P | DED | | | | TB0130G | DED | | | 157, 167-199, 277-299 |
| 145 | 22 | PA | | 3-10 | 31-31-22 | D05566P | 8 | | | | TB0130X | B132 | BJ | | ALL |
| 201B | 24 | PL | A | 3-9 | 32-61-11 | D05566P | 17 | | | | TB0130F | C040 | 2 | | ALL |
| 201R | 24 | PL | A | 0-0 | 32-61-11 | D05566P | 16 | | | | TB0130F | A040 | 2 | | ALL |
| 202B | 24 | PL | B | 3-9 | 32-61-11 | D05566P | 19 | | | | TB0130F | C039 | 2 | | ALL |
| 202R | 24 | PL | B | 0-0 | 32-61-11 | D05566P | 18 | | | | TB0130F | A039 | 2 | | ALL |
| 203B | 24 | PL | C | 3-9 | 32-61-11 | D05566P | 24 | | | | TB0130F | C038 | 2 | | ALL |
| 203R | 24 | PL | C | 0-0 | 32-61-11 | D05566P | 23 | | | | TB0130F | A038 | 2 | | ALL |
| 204B | 24 | PL | D | 3-9 | 27-32-21 | TB0130F | C031 | 2 | | | D04875P | 19 | | | ALL |
| 204R | 24 | PL | D | 0-0 | 27-32-21 | TB0130F | A031 | 2 | | | D04875P | 18 | | | ALL |
| 205B | 24 | PL | E | 3-0 | 32-61-12 | TB0130F | C178 | 2 | | | D05566P | 3 | | | ALL |
| 205R | 24 | PL | E | 0-0 | 32-61-12 | TB0130F | A178 | 2 | | | D05566P | 2 | | | ALL |
| 206B | 24 | PL | F | 3-0 | 32-61-12 | TB0130F | C177 | 2 | | | D05566P | 5 | | | ALL |
| 206R | 24 | PL | F | 0-0 | 32-61-12 | TB0130F | A177 | 2 | | | D05566P | 4 | | | ALL |
| 207B | 24 | PL | G | 2-11 | 32-61-12 | TB0130F | C176 | 2 | | | D05566P | 7 | | | 050-099 |
| 207R | 24 | PL | G | 3-0 | 32-61-12 | TB0130F | C176 | 2 | | | D05566P | 7 | | | 150-199, 275-299 |
| 207R | 24 | PL | G | 0-0 | 32-61-12 | TB0130F | A176 | 2 | | | D05566P | 6 | | | ALL |
| 209B | 24 | PL | I | 2-10 | 32-09-12 | TB0130F | C168 | 2 | | | D05566P | 11 | | | ALL |
| 209R | 24 | PL | I | 0-0 | 32-09-12 | TB0130F | A168 | 2 | | | D05566P | 10 | | | ALL |
| 210B | 24 | PL | J | 2-10 | 32-09-12 | TB0130F | C167 | 2 | | | D05566P | 13 | | | 050-099 |
| 210B | 24 | PL | J | 2-11 | 32-09-12 | TB0130F | C167 | 2 | | | D05566P | 13 | | | 150-199, 275-299 |
| 210R | 24 | PL | J | 0-0 | 32-09-12 | TB0130F | A167 | 2 | | | D05566P | 12 | | | ALL |
| 211B | 24 | PL | K | 3-10 | 32-61-13 | TB0130F | C165 | 2 | | | D04658P | 26 | | | ALL |
| 211R | 24 | PL | K | 0-0 | 32-61-13 | TB0130F | A165 | 2 | | | D04658P | 25 | | | ALL |
| 212B | 24 | PL | L | 4-7 | 32-61-13 | TB0130F | C140 | 2 | | | D04658P | 28 | | | ALL |
| 212R | 24 | PL | L | 0-0 | 32-61-13 | TB0130F | A140 | 2 | | | D04658P | 27 | | | ALL |
| 213B | 24 | PL | M | 4-7 | 32-61-13 | TB0130F | C139 | 2 | | | D04658P | 30 | | | ALL |
| 213R | 24 | PL | M | 0-0 | 32-61-13 | TB0130F | A139 | 2 | | | D04658P | 29 | | | ALL |
| 214B | 24 | PL | N | 4-7 | 32-61-13 | TB0130F | C138 | 2 | | | D04658P | 32 | | | ALL |
| 214R | 24 | PL | N | 0-0 | 32-61-13 | TB0130F | A138 | 2 | | | D04658P | 31 | | | ALL |
| 215W | 24 | 7K | AC | 4-3 | 34-43-21 | D05365P | 1 | | | | TB0205G | 9 | 2 | | ALL |
| 215WB | 24 | 7K | AC | 0-0 | 34-43-21 | D05365P | 2 | | | | TB0205G | 8 | 2 | | ALL |
| 215Z | | | AC | 0-0 | 34-43-21 | D05365P | 3 | | | | TB0205G | REF | | FI | ALL |
| 216B | 24 | PW | AE | 3-10 | 34-43-21 | D05365P | 5 | | | | TB0130H | 25 | 2 | | ALL |
| 216R | 24 | PW | AE | 0-0 | 34-43-21 | D05365P | 4 | | | | TB0130H | 23 | 2 | | ALL |
| 216Z | | | AE | 0-0 | 34-43-21 | D05365P | 6 | | | | GDY0005 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1100 | 286T1100 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | | | |
| 217B | 24 | PW | AD | | 2-11 | 34-43-21 | D05365P | | 12 | | | | TB0130G | 162 | 2 | | 050-099 |
| 217B | 24 | PW | AD | | 5-0 | 34-43-21 | D05365P | | 12 | | | | TB0130G | 162 | 2 | | 150-199, 275-299 |
| 217R | 24 | PW | AD | | 0-0 | 34-43-21 | D05365P | | 11 | | | | TB0130G | 161 | 2 | | ALL |
| 217Z | | | AD | | 0-0 | 34-43-21 | D05365P | | 13 | | | | GDY0010 | S.. | 2 | | 050-099, 277-299 |
| 217Z | | | AD | | 0-0 | 34-43-21 | D05365P | | 13 | | | | GDY0009 | S.. | 2 | | 150-199, 275-276 |
| 218W | 24 | 7K | AV | | 4-8 | 34-43-11 | D04875P | | 21 | | | | TB0205G | 9 | 2 | | ALL |
| 218WB | 24 | 7K | AV | | 0-0 | 34-43-11 | D04875P | | 22 | | | | TB0205G | 8 | 2 | | ALL |
| 218Z | | | AV | | 0-0 | 34-43-11 | D04875P | | 23 | | | | TB0205G | REF | | FE | ALL |
| 220R | 20 | RJ | H | | 3-7 | 77-31-11 | D05430P | | 4 | | | | D05638P | 10 | | | 050-099 |
| 220R | 20 | RJ | H | | 3-6 | 77-31-11 | D05430P | | 4 | | | | D05638P | 10 | | | 150-199, 275-299 |
| 220W | 20 | RJ | H | | 0-0 | 77-31-11 | D05430P | | 5 | | | | D05638P | 11 | | | ALL |
| 220Z | | | H | | 0-0 | 77-31-11 | D05430P | | 6 | | | | D05638P | 12 | | | ALL |
| 221B | 24 | PL | T | | 3-5 | 78-34-21 | TB0130F | A082 | 2 | | | | D05428P | 1 | | | ALL |
| 221R | 24 | PL | T | | 0-0 | 78-34-21 | TB0130F | C082 | 2 | | | | D05428P | 2 | | | ALL |
| 222B | 24 | PL | U | | 3-5 | 78-34-21 | TB0130F | A081 | 2 | | | | D05428P | 3 | | | ALL |
| 222R | 24 | PL | U | | 0-0 | 78-34-21 | TB0130F | C081 | 2 | | | | D05428P | 4 | | | ALL |
| 223B | 24 | PL | V | | 3-11 | 78-36-21 | TB0130F | C071 | 2 | | | | D05430P | 11 | | | ALL |
| 223R | 24 | PL | V | | 0-0 | 78-36-21 | TB0130F | A071 | 2 | | | | D05430P | 12 | | | ALL |
| 224B | 24 | PL | W | | 3-11 | 78-36-21 | TB0130F | C070 | 2 | | | | D05430P | 13 | | | ALL |
| 224R | 24 | PL | W | | 0-0 | 78-36-21 | TB0130F | A070 | 2 | | | | D05430P | 14 | | | ALL |
| 225B | 24 | PL | X | | 3-9 | 78-36-21 | TB0130F | C080 | 2 | | | | D05430P | 9 | | | ALL |
| 225R | 24 | PL | X | | 0-0 | 78-36-21 | TB0130F | A080 | 2 | | | | D05430P | 10 | | | ALL |
| 226B | 24 | PL | Y | | 4-1 | 78-36-21 | TB0130F | C068 | 2 | | | | D05430P | 7 | | | ALL |
| 226R | 24 | PL | Y | | 0-0 | 78-36-21 | TB0130F | A068 | 2 | | | | D05430P | 8 | | | ALL |
| 227B | 24 | PW | Z | | 3-7 | 22-41-11 | D04875P | | 13 | | | | TB0130F | C150 | 2 | | ALL |
| 227R | 24 | PW | Z | | 0-0 | 22-41-11 | D04875P | | 12 | | | | TB0130F | A150 | 2 | | ALL |
| 227Z | | | Z | | 0-0 | 22-41-11 | D04875P | | 14 | | | | GDY0008 | S.. | 2 | | ALL |
| 228B | 24 | PW | AA | | 3-7 | 22-41-11 | D04875P | | 4 | | | | TB0130F | C151 | 2 | | ALL |
| 228R | 24 | PW | AA | | 0-0 | 22-41-11 | D04875P | | 3 | | | | TB0130F | A151 | 2 | | ALL |
| 228Z | | | AA | | 0-0 | 22-41-11 | D04875P | | 5 | | | | GDY0008 | S.. | 2 | | ALL |
| 231B | 24 | PW | AT | | 3-5 | 77-12-12 | D05140P | | 18 | | | | D05638P | 13 | | | 050-099 |
| 231B | 24 | PW | AT | | 5-10 | 77-12-12 | D05140P | | 18 | | | | D05638P | 13 | | | 150-199, 275-299 |
| 231R | 24 | PW | AT | | 0-0 | 77-12-12 | D05140P | | 19 | | | | D05638P | 14 | | | ALL |
| 231Z | | | AT | | 0-0 | 77-12-12 | D05140P | | 17 | | | | D05638P | 15 | | | ALL |
| 232B | 24 | PW | JG | | 4-8 | 77-31-11 | D06278P | | 11 | | | | TB0130Y | C042 | BJ | | 050-099 |
| 232B | 24 | PW | AU | | 4-8 | 77-31-11 | D06278P | | 11 | | | | TB0130Y | C042 | BJ | | 150-199, 275-299 |
| 232R | 24 | PW | JG | | 0-0 | 77-31-11 | D06278P | | 10 | | | | TB0130Y | A042 | BJ | | 050-099 |
| 232R | 24 | PW | AU | | 0-0 | 77-31-11 | D06278P | | 10 | | | | TB0130Y | A042 | BJ | | 150-199, 275-299 |
| 232Z | | | JG | | 0-0 | 77-31-11 | D06278P | | 12 | | | | GDY0007 | S.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1100 | 286T1100 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | |
| 232Z | | | | AU | 0-0 | 77-31-11 | D06278P | | 12 | | GDY0008 | S.. | 2 | | 150-199, 275-276 |
| 232Z | | | | AU | 0-0 | 77-31-11 | D06278P | | 12 | | GDY0007 | S.. | 2 | | 277-299 |
| 260B | 24 | PW | BK | | 3-6 | 22-12-21 | D04875P | | 10 | | TB0130F | C153 | 2 | | ALL |
| 260R | 24 | PW | BK | | 0-0 | 22-12-21 | D04875P | | 9 | | TB0130F | A153 | 2 | | ALL |
| 260Z | | | | BK | 0-0 | 22-12-21 | D04875P | | 11 | | GDY0009 | S.. | 2 | | ALL |
| 261B | 24 | PL | BJ | | 3-1 | 32-09-12 | D04658P | | 17 | | TB0130F | A096 | 2 | | ALL |
| 261R | 24 | PL | BJ | | 0-0 | 32-09-12 | D04658P | | 16 | | TB0130F | C096 | 2 | | ALL |
| 269B | 24 | PW | BR | | 3-4 | 21-31-11 | D04875P | | 7 | | TB0130F | C064 | 2 | | ALL |
| 269R | 24 | PW | BR | | 0-0 | 21-31-11 | D04875P | | 6 | | TB0130F | A064 | 2 | | ALL |
| 269Z | | | | BR | 0-0 | 21-31-11 | D04875P | | 8 | | TB0130F | A063 | 2 | | ALL |
| 273B | 24 | PW | AF | | 4-10 | 34-22-18 | D04545P | | 7 | | TB0130F | C115 | 2 | | ALL |
| 273R | 24 | PW | AF | | 0-0 | 34-22-18 | D04545P | | 6 | | TB0130F | A115 | 2 | | ALL |
| 273Z | | | | AF | 0-0 | 34-22-18 | D04545P | | 8 | | GDY0002 | S.. | 2 | | ALL |
| 274B | 24 | PW | KX | | 3-10 | 34-22-19 | D05613J | | 12 | | TB0130F | C102 | 2 | | ALL |
| 274R | 24 | PW | KX | | 0-0 | 34-22-19 | D05613J | | 11 | | TB0130F | A102 | 2 | | ALL |
| 274Z | | | | KX | 0-0 | 34-22-19 | D05613J | | 13 | | GDY0001 | S.. | 2 | | 050-099, 157-199, 275-299 |
| 274Z | | | | KX | 0-0 | 34-22-19 | D05613J | | 13 | | GDY0002 | S.. | 2 | | 150-156 |
| 275B | 24 | PW | AG | | 3-10 | 73-21-14 | D05613J | | 15 | | TB0130F | C103 | 2 | | ALL |
| 275R | 24 | PW | AG | | 0-0 | 73-21-14 | D05613J | | 14 | | TB0130F | A103 | 2 | | ALL |
| 275Z | | | | AG | 0-0 | 73-21-14 | D05613J | | 16 | | TB0130F | A104 | 2 | | ALL |
| 279B | 24 | PW | LD | | 2-7 | 77-12-11 | D05613J | | 2 | | TB0130Y | C043 | BJ | | 150-157, 275-276 |
| 279R | 24 | PW | LD | | 0-0 | 77-12-11 | D05613J | | 3 | | TB0130Y | A043 | BJ | | 150-157, 275-276 |
| 279Z | | | | LD | 0-0 | 77-12-11 | D05613J | | 1 | | GDY0008 | S.. | 2 | | 150-157, 275-276 |
| 280B | 24 | PW | KE | | 4-8 | 77-12-11 | D05638P | | 22 | | TB0130Y | C042 | BJ | | 050-099 |
| 280B | 24 | PW | LE | | 4-8 | 77-12-11 | D05638P | | 22 | | TB0130Y | C042 | BJ | | 150-199, 275-299 |
| 280R | 24 | PW | KE | | 0-0 | 77-12-11 | D05638P | | 21 | | TB0130Y | A042 | BJ | | 050-099 |
| 280R | 24 | PW | LE | | 0-0 | 77-12-11 | D05638P | | 21 | | TB0130Y | A042 | BJ | | 150-199, 275-299 |
| 280Z | | | | KE | 0-0 | 77-12-11 | D05638P | | 23 | | GDY0007 | S.. | 2 | | 050-099 |
| 280Z | | | | LE | 0-0 | 77-12-11 | D05638P | | 23 | | GDY0008 | S.. | 2 | | 150-199, 275-276 |
| 280Z | | | | LE | 0-0 | 77-12-11 | D05638P | | 23 | | GDY0007 | S.. | 2 | | 277-299 |
| 281B | 22 | PR | LF | | 3-8 | 31-31-22 | D05566P | | 29 | | TB0130X | A133 | BJ | | ALL |
| 281R | 22 | PR | LF | | 0-0 | 31-31-22 | D05566P | | 28 | | TB0130X | A132 | BJ | | ALL |
| 281Z | | | | LF | 0-0 | 31-31-22 | D05566P | | 30 | | GDY0007 | S.. | 2 | | ALL |
| 282B | 22 | PR | LG | | 3-8 | 32-45-14 | D05566P | | 21 | | TB0130X | A044 | BJ | | 050-099, 150-199 |
| 282R | 22 | PR | LG | | 0-0 | 32-45-14 | D05566P | | 22 | | TB0130X | B044 | BJ | | 050-099, 150-199 |
| 282Z | | | | LG | 0-0 | 32-45-14 | D05566P | | 1 | | TB0130X | A045 | BJ | | 050-099, 150-199 |
| 283B | 22 | PR | LH | | 3-8 | 32-45-14 | D05566P | | 31 | | TB0130X | C044 | BJ | | 050-099, 150-199 |
| 283R | 22 | PR | LH | | 0-0 | 32-45-14 | D05566P | | 32 | | TB0130X | D044 | BJ | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|-------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1100 | 286T1100 | | | E1-2 INTEGRATION (continued) | | | | | | | | | | | | |
| 283Z | | | LH | 0-0 | 32-45-14 | D05566P | | 26 | | | TB0130X | B045 | BJ | | 050-099, 150-199 | |
| 284B | 22 | | PR LI | 3-8 | 32-45-14 | D05566P | | 33 | | | TB0130X | A046 | BJ | | 050-099, 150-199 | |
| 284R | 22 | | PR LI | 0-0 | 32-45-14 | D05566P | | 34 | | | TB0130X | B046 | BJ | | 050-099, 150-199 | |
| 284Z | | | LI | 0-0 | 32-45-14 | D05566P | | 35 | | | TB0130X | C045 | BJ | | 050-099, 150-199 | |
| 285B | 22 | | PR LJ | 3-8 | 32-45-14 | D05566P | | 36 | | | TB0130X | C046 | BJ | | 050-099, 150-199 | |
| 285R | 22 | | PR LJ | 0-0 | 32-45-14 | D05566P | | 37 | | | TB0130X | D046 | BJ | | 050-099, 150-199 | |
| 285Z | | | LJ | 0-0 | 32-45-14 | D05566P | | 38 | | | TB0130X | D045 | BJ | | 050-099, 150-199 | |
| 286B | 24 | | PW AL | 4-2 | 36-23-21 | D04658P | | 4 | | | TB0130F | C056 | 2 | | 156-162, 166-199, 277-299 | |
| 286R | 24 | | PW AL | 0-0 | 36-23-21 | D04658P | | 5 | | | TB0130F | A056 | 2 | | 156-162, 166-199, 277-299 | |
| 286Z | | | AL | 0-0 | 36-23-21 | D04658P | | 6 | | | GDY0009 | S.. | 2 | | 156-162, 166-199, 277-299 | |
| 501 | 24 | | PV BT | 4-0 | 78-36-11 | D05428P | | 17 | | | TB0130F | A048 | 2 | | ALL | |
| 501Z | | | BT | 0-0 | 78-36-11 | D05428P | | DED | | | TB0130F | DED | | | ALL | |
| 502 | 24 | | PV BU | 4-0 | 78-36-11 | D05428P | | 18 | | | TB0130F | C048 | 2 | | ALL | |
| 502Z | | | BU | 0-0 | 78-36-11 | D05428P | | DED | | | TB0130F | DED | | | ALL | |
| 507 | 24 | | PK | 4-3 | 31-31-26 | D05430P | | 15 | | | D04875P | 27 | | | ALL | |
| 901W | 24 | | PW AP | 1-0 | 34-43-21 | D05365P | | 7 | | | D05365P | 14 | | | 150, 152-199, 275-299 | |
| 901WB | 24 | | PW AP | 0-0 | 34-43-21 | D05365P | | 8 | | | D05365P | 15 | | | 150, 152-199, 275-299 | |
| 901Z | | | AP | 0-0 | 34-43-21 | D05365P | | 9 | | | D05365P | 10 | | | 150, 152-199, 275-299 | |
| FRE | | | | 0-3 | 34-43-11 | GDZ0001 | | S.. | 2 | | TB0205G | REF | | FE | ALL | |
| FRI | | | | 0-3 | 34-43-21 | GDZ0001 | | S.. | 2 | | TB0205G | REF | | FI | ALL | |
| W1101 | 286T1101 | | | E1-1 SHELF | | | | | | | | | | | | |
| 001 | 22 | | PQ AA | 2-1 | 22-21-11 | D01259B | | G08 | | | D05307J | 1 | | | ALL | |
| 001Z | | | AA | 0-0 | 22-21-11 | D01259B | | DED | | | D05307J | DED | | | ALL | |
| 002 | 22 | | PA | 2-1 | 22-21-11 | D01259B | | G07 | | | D05307J | 3 | | | ALL | |
| 003 | 22 | | PA | 3-2 | 22-21-11 | TB0101G | | 21 | 2 | | D05307J | 22 | | | ALL | |
| 004 | 22 | | PA | 3-2 | 22-21-11 | TB0101G | | 21 | 2 | | D05307J | 2 | | | ALL | |
| 005 | 22 | | PA | 2-10 | 22-21-11 | TB0101G | | 21 | 2 | | D01259B | F07 | | | ALL | |
| 006 | 22 | | PA | 3-2 | 22-21-11 | TB0101G | | 21 | 2 | | D05997J | 2 | | | ALL | |
| 007 | 22 | | PA | 2-1 | 22-21-11 | D01259B | | F08 | | | D05997J | 3 | | | ALL | |
| 008 | 22 | | PQ AH | 2-9 | 22-21-11 | D01259B | | K10 | | | TB0101H | 121 | 2 | | ALL | |
| 008Z | | | AH | 0-0 | 22-21-11 | D01259B | | DED | | | TB0101H | DED | | | ALL | |
| 010 | 22 | | PA | 2-7 | 22-22-11 | D00665B | | B05 | | | D05997J | 4 | | | ALL | |
| 015 | 22 | | PA | 3-3 | 27-09-14 | D05307J | | 34 | | | TB0101G | 31 | 2 | | ALL | |
| 016 | 22 | | PQ AP | 3-6 | 27-09-11 | D01253B | | K15 | | | TB0101H | 121 | 2 | | ALL | |
| 016Z | | | AP | 0-0 | 27-09-11 | D01253B | | DED | | | TB0101H | DED | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1101 | 286T1101 | | | E1-1 SHELF (continued) | | | | | | | | | | | |
| 017 | 22 | | PA | | 3-3 | 27-09-14 | D05307J | | 35 | | TB0101G | 32 | 2 | | ALL |
| 018 | 22 | | PQ | AR | 3-2 | 27-09-11 | D01251B | | K15 | | TB0101H | 121 | 2 | | ALL |
| 018Z | | | | AR | 0-0 | 27-09-11 | D01251B | | DED | | TB0101H | DED | | | ALL |
| 019 | 22 | | PQ | AS | 2-5 | 27-09-11 | D05325J | | 3 | | TB0101H | 121 | 2 | | ALL |
| 019Z | | | | AS | 0-0 | 27-09-11 | D05325J | | DED | | TB0101H | DED | | | ALL |
| 020 | 22 | | PQ | AT | 3-1 | 27-09-11 | D01251B | | E15 | | D05325J | 2 | | | ALL |
| 020Z | | | | AT | 0-0 | 27-09-11 | D01251B | | DED | | D05325J | DED | | | ALL |
| 021 | 22 | | PA | | 3-3 | 27-09-14 | D05307J | | 36 | | TB0101G | 33 | 2 | | ALL |
| 022 | 22 | | PA | | 3-2 | 27-09-14 | D01251B | | K13 | | TB0101G | 125 | 2 | | ALL |
| 023 | 22 | | PA | | 2-7 | 27-09-14 | D01263B | | D14 | | TB0101G | 33 | 2 | | ALL |
| 024 | 22 | | PA | | 2-10 | 27-09-14 | D01259B | | G10 | | TB0101G | 31 | 2 | | ALL |
| 025 | 22 | | PA | | 2-4 | 27-09-14 | D00665B | | A15 | | TB0101G | 32 | 2 | | ALL |
| 026 | 22 | | PA | | 3-4 | 27-09-14 | D00829A | | H14 | | TB0101H | 123 | 2 | | ALL |
| 027 | 22 | | PA | | 3-2 | 27-09-14 | D05307J | | 8 | | TB0101G | 125 | 2 | | ALL |
| 028 | 22 | | PA | | 2-5 | 27-09-14 | D05997J | | 11 | | D05307J | 11 | | | ALL |
| 029 | 22 | | PA | | 3-2 | 27-09-14 | D05307J | | 25 | | TB0101H | 123 | 2 | | ALL |
| 030 | 22 | | PA | | 2-5 | 27-09-14 | TB0101H | | 123 | 2 | D00827A | H14 | | | ALL |
| 031 | 22 | | PA | | 2-11 | 27-09-14 | TB0101H | | 123 | 2 | D00825A | H14 | | | ALL |
| 032 | 22 | | PA | | 3-6 | 27-09-14 | TB0101G | | 125 | 2 | D01253B | K13 | | | ALL |
| 033 | 20 | | PQ | BH | 2-6 | 27-11-12 | TB0101G | | 23 | 2 | D05325J | 4 | | | ALL |
| 033Z | | | | BH | 0-0 | 27-11-12 | TB0101G | | DED | | D05325J | DED | | | ALL |
| 034 | 22 | | PQ | BI | 2-4 | 27-11-12 | TB0101G | | 23 | 2 | D00665B | B01 | | | ALL |
| 034Z | | | | BI | 0-0 | 27-11-12 | TB0101G | | DED | | D00665B | DED | | | ALL |
| 035 | 22 | | PQ | BJ | 2-4 | 27-11-12 | TB0101G | | 23 | 2 | D00665B | A01 | | | ALL |
| 035Z | | | | BJ | 0-0 | 27-11-12 | TB0101G | | DED | | D00665B | DED | | | ALL |
| 036 | 22 | | PA | | 2-4 | 27-11-12 | TB0101G | | 24 | 2 | D00665B | A04 | | | ALL |
| 037 | 20 | | PA | | 3-2 | 27-11-12 | TB0101G | | 24 | 2 | D05307J | 19 | | | ALL |
| 038 | 20 | | PA | | 3-2 | 27-11-12 | TB0101G | | 24 | 2 | D05997J | 12 | | | ALL |
| 039 | 22 | | PA | | 2-4 | 27-11-12 | TB0101G | | 25 | 2 | D00665B | A03 | | | ALL |
| 040 | 20 | | PA | | 3-2 | 27-11-12 | TB0101G | | 25 | 2 | D05307J | 18 | | | ALL |
| 041 | 20 | | PA | | 3-2 | 27-11-12 | TB0101G | | 25 | 2 | D05997J | 13 | | | ALL |
| 042 | 22 | | PA | | 2-4 | 27-11-12 | D00665B | | B12 | | TB0101G | 26 | 2 | | ALL |
| 043 | 22 | | PA | | 3-2 | 27-11-12 | D05307J | | 16 | | TB0101G | 26 | 2 | | ALL |
| 044 | 22 | | PA | | 3-2 | 27-11-12 | D05997J | | 14 | | TB0101G | 26 | 2 | | ALL |
| 045 | 22 | | PA | | 2-4 | 27-11-12 | D00665B | | B14 | | TB0101G | 27 | 2 | | ALL |
| 046 | 22 | | PA | | 3-3 | 27-11-12 | D05307J | | 17 | | TB0101G | 27 | 2 | | ALL |
| 047 | 22 | | PA | | 3-2 | 27-11-12 | D05997J | | 15 | | TB0101G | 27 | 2 | | ALL |
| 048 | 22 | | PA | | 2-7 | 27-11-12 | D05997J | | 16 | | D00665B | B13 | | | ALL |
| 049 | 22 | | PA | | 2-7 | 27-11-12 | D05997J | | 17 | | D00665B | B15 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1100
Page 6
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1101 | 286T1101 | | | E1-1 SHELF (continued) | | | | | | | | | | | | |
| 050 | 22 | | PA | 2-3 | 27-11-12 | TB0101G | 126 | 2 | | D00665B | A11 | | | ALL | | |
| 051 | 22 | | PA | 3-5 | 27-11-12 | TB0101G | 126 | 2 | | D05997J | 18 | | | ALL | | |
| 052 | 22 | | PA | 3-2 | 27-11-12 | TB0101G | 126 | 2 | | D05307J | 21 | | | ALL | | |
| 053 | 22 | | PA | 3-2 | 27-11-12 | TB0101G | 126 | 2 | | D05307J | 4 | | | ALL | | |
| 054 | 22 | | PA | 2-7 | 27-21-12 | TB0101G | 127 | 2 | | D01263B | A14 | | | ALL | | |
| 055 | 22 | | PA | 3-2 | 27-21-12 | TB0101G | 127 | 2 | | D05307J | 5 | | | ALL | | |
| 056 | 22 | | PA | 3-2 | 27-21-12 | TB0101G | 127 | 2 | | D05307J | 23 | | | ALL | | |
| 057 | 22 | | PA | 3-5 | 27-21-12 | TB0101G | 127 | 2 | | D05997J | 19 | | | ALL | | |
| 058 | 22 | | PA | 2-4 | 27-41-11 | D00665B | | C11 | | TB0101G | 28 | 2 | | ALL | | |
| 059 | 22 | | PA | 3-2 | 27-41-11 | D05997J | | 20 | | TB0101G | 28 | 2 | | ALL | | |
| 060 | 22 | | PA | 3-3 | 27-41-11 | D05307J | | 14 | | TB0101G | 28 | 2 | | ALL | | |
| 061 | 22 | | PA | 3-3 | 27-41-11 | D05307J | | 10 | | TB0101G | 29 | 2 | | ALL | | |
| 062 | 22 | | PA | 2-4 | 27-41-11 | D00665B | | C13 | | TB0101G | 29 | 2 | | ALL | | |
| 063 | 22 | | PA | 3-2 | 27-41-11 | D05997J | | 21 | | TB0101G | 29 | 2 | | ALL | | |
| 064 | 22 | | PA | 3-3 | 27-41-11 | D05307J | | 13 | | TB0101G | 29 | 2 | | ALL | | |
| 067 | 22 | | PA | 3-9 | 27-61-12 | D00829A | | C14 | | D00825A | C15 | | | ALL | | |
| 068 | 22 | | PA | 3-3 | 27-61-12 | D00829A | | C15 | | D00827A | C14 | | | ALL | | |
| 069 | 22 | | PA | 2-1 | 27-61-12 | D00827A | | C15 | | D00825A | C14 | | | ALL | | |
| 071 | 22 | | PA | 3-3 | 27-41-11 | D05307J | | 24 | | TB0101G | 28 | 2 | | ALL | | |
| 072 | 22 | | PA | 3-3 | 27-61-12 | D00829A | | H15 | | TB0101H | 128 | 2 | | ALL | | |
| 073 | 22 | | PA | 2-5 | 27-61-12 | D00827A | | H15 | | TB0101H | 128 | 2 | | ALL | | |
| 074 | 22 | | PA | 2-11 | 27-61-12 | D00825A | | H15 | | TB0101H | 128 | 2 | | ALL | | |
| 075 | 22 | | PA | 3-2 | 27-61-12 | D05307J | | 12 | | TB0101H | 128 | 2 | | ALL | | |
| 076 | 22 | | PA | 3-2 | 27-61-12 | D05307J | | 6 | | TB0101H | 128 | 2 | | ALL | | |
| 077 | 22 | | PA | 3-1 | 27-61-12 | D05997J | | 22 | | TB0101H | 128 | 2 | | ALL | | |
| 081 | 22 | | PA | 3-3 | 27-61-12 | D00829A | | G13 | | D00827A | D13 | | | ALL | | |
| 082 | 22 | | PA | 3-3 | 27-61-12 | D00827A | | F13 | | D00829A | E13 | | | ALL | | |
| 083 | 22 | | PA | 3-3 | 27-61-12 | D00829A | | G14 | | D00827A | D14 | | | ALL | | |
| 084 | 22 | | PA | 3-3 | 27-61-12 | D00829A | | E14 | | D00827A | F14 | | | ALL | | |
| 085 | 22 | | PA | 3-3 | 27-61-12 | D00829A | | G15 | | D00827A | E15 | | | ALL | | |
| 086 | 22 | | PA | 3-3 | 27-61-12 | D00829A | | D15 | | D00827A | F15 | | | ALL | | |
| 087 | 22 | | PA | 3-9 | 27-61-12 | D00829A | | F13 | | D00825A | E13 | | | ALL | | |
| 088 | 22 | | PA | 3-9 | 27-61-12 | D00829A | | D13 | | D00825A | G13 | | | ALL | | |
| 089 | 22 | | PA | 3-9 | 27-61-12 | D00829A | | F14 | | D00825A | E14 | | | ALL | | |
| 090 | 22 | | PA | 3-9 | 27-61-12 | D00829A | | D14 | | D00825A | G14 | | | ALL | | |
| 091 | 22 | | PA | 3-9 | 27-61-12 | D00829A | | F15 | | D00825A | D15 | | | ALL | | |
| 092 | 22 | | PA | 3-9 | 27-61-12 | D00829A | | E15 | | D00825A | G15 | | | ALL | | |
| 093 | 22 | | PA | 2-1 | 27-61-12 | D00825A | | D13 | | D00827A | G13 | | | ALL | | |
| 094 | 22 | | PA | 2-1 | 27-61-12 | D00825A | | F13 | | D00827A | E13 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1101 | 286T1101 | | | E1-1 SHELF (continued) | | | | | | | | | | | |
| 095 | 22 | | PA | | 2-1 | 27-61-12 | D00825A | | D14 | | D00827A | | G14 | | ALL |
| 096 | 22 | | PA | | 2-1 | 27-61-12 | D00825A | | F14 | | D00827A | | E14 | | ALL |
| 097 | 22 | | PA | | 2-1 | 27-61-12 | D00825A | | E15 | | D00827A | | G15 | | ALL |
| 098 | 22 | | PA | | 2-1 | 27-61-12 | D00825A | | F15 | | D00827A | | D15 | | ALL |
| 099 | 22 | | PA | | 2-6 | 27-61-12 | D05307J | | 28 | | D00829A | | H13 | | ALL |
| 100 | 22 | | PA | | 3-1 | 27-61-12 | D05307J | | 27 | | D00827A | | H13 | | ALL |
| 101 | 22 | | PA | | 3-8 | 27-61-12 | D05307J | | 26 | | D00825A | | H13 | | ALL |
| 102 | 22 | | PA | | 2-5 | 27-61-12 | D05307J | | 29 | | D05997J | | 29 | | ALL |
| 103 | 22 | | PA | | 2-5 | 27-61-12 | D05307J | | 30 | | D05997J | | 30 | | ALL |
| 104 | 22 | | PA | | 2-5 | 27-61-12 | D05307J | | 31 | | D05997J | | 28 | | ALL |
| 109 | 22 | | PQ | EI | 2-11 | 27-61-14 | D00825A | | K15 | | TB0101H | | 121 | 2 | ALL |
| 109Z | | | | EI | 0-0 | 27-61-14 | D00825A | | DED | | TB0101H | | DED | | ALL |
| 111 | 22 | | PQ | EK | 2-5 | 27-61-15 | D00827A | | K15 | | TB0101H | | 121 | 2 | ALL |
| 111Z | | | | EK | 0-0 | 27-61-15 | D00827A | | DED | | TB0101H | | DED | | ALL |
| 113 | 22 | | PQ | EM | 3-4 | 27-61-16 | D00829A | | K15 | | TB0101H | | 121 | 2 | ALL |
| 113Z | | | | EM | 0-0 | 27-61-16 | D00829A | | DED | | TB0101H | | DED | | ALL |
| 116 | 22 | | PA | | 3-1 | 27-09-14 | D05997J | | 6 | | TB0101H | | 123 | 2 | ALL |
| 117 | 22 | | PA | | 3-2 | 27-09-14 | D05997J | | 7 | | TB0101G | | 31 | 2 | ALL |
| 118 | 22 | | PA | | 3-2 | 27-09-14 | D05997J | | 8 | | TB0101G | | 32 | 2 | ALL |
| 119 | 22 | | PA | | 3-2 | 27-09-14 | D05997J | | 9 | | TB0101G | | 33 | 2 | ALL |
| 121 | 22 | | PA | | 1-10 | 22-21-11 | D01259A | | CAP | Y | GDX0007 | | D.. | 2 | 150-199, 275-299 |
| 122 | 22 | | PA | | 1-10 | 22-21-11 | D01259A | | CAP | Y | GDX0007 | | D.. | 2 | 150-199, 275-299 |
| 123 | 22 | | PA | | 4-0 | 27-41-31 | D05997J | | 10 | | TB0101G | | 102 | 2 | 050-099, 155-199, 275-299 |
| W1102 | 286T1102 | | | P19 INTEGRATION | | | | | | | | | | | |
| 007 | 22 | | PA | | 2-7 | 33-24-11 | TB0146Y | | C016 | BJ | D04326J | | 13 | | ALL |
| 009 | 22 | | PA | | 2-5 | 33-25-11 | TB0146Y | | A005 | BJ | D04326J | | 7 | | ALL |
| 011 | 22 | | PA | | 2-5 | 33-26-11 | TB0146Y | | A006 | BJ | D04326J | | 4 | | 050-099, 275-299 |
| 011 | 22 | | PA | | 3-0 | 33-26-11 | TB0174Z | | 36 | BJ | D04326J | | 4 | | 150-199 |
| 012 | 22 | | PA | | 3-1 | 33-26-11 | TB0146Z | | 36 | BJ | D04326J | | 3 | | 050-099, 275-299 |
| 013 | 20 | | PA | | 3-1 | 33-26-21 | TB0146Z | | 35 | BJ | D04326J | | 6 | | ALL |
| 014 | 16 | | PA | | 2-3 | 38-13-11 | D04326J | | 21 | FM | TB0146G | | 4 | 2 | 050-099 |
| 014 | 16 | | PA | | 2-3 | 38-13-11 | D04326J | | 21 | | TB0146G | | 4 | 2 | 275-299 |
| 015 | 16 | | PA | | 3-11 | 38-13-11 | D04282J | | 7 | | TB0146G | | 4 | 2 | ALL |
| 018 | 18 | | PA | | 3-6 | 21-24-11 | D05072J | | 5 | | D04282J | | 4 | | 050-099, 150-199 |
| 019 | 18 | | PA | | 3-6 | 21-24-11 | D05072J | | 6 | | D04282J | | 6 | | 050-099, 150-199 |
| 020 | 18 | | PA | | 3-6 | 21-24-11 | D05072J | | 7 | | D04282J | | 8 | | 050-099, 150-199 |
| 021 | 24 | | PK | | 2-4 | 21-24-11 | D05072J | | 8 | | TB0146F | | C003 | 2 | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1102 | 286T1102 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 022 | 16 | | PA | 2-3 | 38-13-11 | D04326J | 23 | FM | | | | | TB0146G | 4 | 2 | | 050-099 |
| 022 | 16 | | PA | 2-3 | 38-13-11 | D04326J | 40 | | | | | | TB0146G | 4 | 2 | | 150-199 |
| 022 | 16 | | PA | 2-3 | 38-13-11 | D04326J | 23 | | | | | | TB0146G | 4 | 2 | | 275-299 |
| 023 | 22 | | PA | 3-0 | 33-26-11 | D04326J | 2 | | | | | | TB0174Z | 36 | BJ | | 150-199 |
| 023 | 22 | | PA | 2-5 | 33-26-11 | D04326J | 2 | | | | | | TB0146Y | A006 | BJ | | 275-299 |
| 024 | 22 | | PA | 2-5 | 38-32-12 | D04326J | 17 | | | | | | TB0146X | C008 | BJ | | 050-099 |
| 024 | 20 | | PA | 2-5 | 38-32-12 | D04326J | 17 | | | | | | TB0146X | C008 | BJ | | 150-156, 162-165, 275-276 |
| 024 | 20 | | PA | 2-5 | 38-32-16 | D04326J | 17 | | | | | | TB0146X | C008 | BJ | | 157, 166-199, 277-299 |
| 034 | 20 | | PA | 2-11 | 33-26-11 | D04326J | 19 | | | | | | TB0146Y | A028 | BJ | | 050-099 |
| 034 | 20 | | PA | 3-1 | 33-26-11 | D04326J | 19 | | | | | | TB0146Z | 35 | BJ | | 150-199, 275-299 |
| 036 | 20 | | PA | 4-10 | 38-32-12 | D04282J | 5 | | | | | | TB0146Y | A037 | BJ | | 050-099, 150-156, 162-165, 275-276 |
| 039 | 20 | | PA | 3-2 | 38-32-12 | D04326J | 26 | | | | | | TB0146Y | A037 | BJ | | 050-099, 275-276 |
| 039 | 20 | | PA | 3-2 | 38-32-12 | D04326J | 42 | | | | | | TB0146Y | A037 | BJ | | 150-156, 162-165 |
| 039 | 20 | | PA | 3-2 | 38-32-16 | D04326J | 42 | | | | | | TB0146Y | A037 | BJ | | 157, 166-199 |
| 039 | 20 | | PA | 3-2 | 38-32-16 | D04326J | 26 | | | | | | TB0146Y | A037 | BJ | | 277-299 |
| 040 | 20 | | PA | 3-2 | 38-32-12 | D04326J | 24 | | | | | | TB0146Y | A037 | BJ | | 050-099, 275-276 |
| 040 | 20 | | PA | 3-2 | 38-32-12 | D04326J | 41 | | | | | | TB0146Y | A037 | BJ | | 150-156, 162-165 |
| 040 | 20 | | PA | 3-2 | 38-32-16 | D04326J | 41 | | | | | | TB0146Y | A037 | BJ | | 157, 166-199 |
| 040 | 20 | | PA | 3-2 | 38-32-16 | D04326J | 24 | | | | | | TB0146Y | A037 | BJ | | 277-299 |
| 042 | 20 | | PA | 2-5 | 33-26-21 | D04326J | 15 | | | | | | TB0146X | D008 | BJ | | 280-299 |
| 051 | 22 | | PA | 2-7 | 33-24-11 | TB0146Z | 14 | BJ | | | | | D04326J | 35 | | | 150-199 |
| 052 | 22 | | PA | 2-7 | 33-24-11 | TB0146Z | 13 | BJ | | | | | D04326J | 25 | | | 150-199 |
| 078 | 20 | | PA | 2-6 | 33-26-21 | D04326J | 15 | | | | | | TB0146X | A009 | BJ | | 050-099 |
| 081 | 20 | | PA | 3-2 | 26-13-11 | D04326J | 32 | | | | | | TB0174Z | 42 | BJ | | 050-099 |
| 082 | 20 | | PA | 3-2 | 26-13-11 | D04326J | 33 | | | | | | TB0174Z | 43 | BJ | | 050-099 |
| 083 | 20 | | PA | 3-2 | 26-13-11 | D04326J | 34 | | | | | | TB0174Z | 41 | BJ | | 050-099 |
| 084 | 20 | | PA | 2-11 | 26-13-11 | D04326J | 31 | | | | | | TB0174X | D031 | BJ | | 050-099 |
| 086 | 22 | | PA | 2-8 | 33-25-11 | TB0146Y | | C017 | BJ | | | | D04326J | 39 | | | 050-099 |
| 102 | 20 | | PA | 4-2 | 25-42-11 | D04282J | 1 | | | | | | TB0146Y | A011 | BJ | | ALL |
| 104 | 20 | | PA | 2-6 | 25-42-11 | TB0146Y | | A011 | BJ | | | | D04326J | 36 | | | 050-099 |
| 104 | 20 | | PA | 2-6 | 25-42-11 | D04326J | 36 | | | | | | TB0146Y | A011 | BJ | | 150-199, 275-299 |
| 105 | 20 | | PA | 2-9 | 33-26-21 | D04326J | 43 | | | | | | TB0160Y | C017 | BJ | | 050-099 |
| 105 | 20 | | PA | 2-9 | 33-26-21 | TB0160Y | | C017 | BJ | | | | D04326J | 43 | | | 150-157 |
| 105 | 20 | | PA | 2-5 | 33-26-21 | TB0146X | | A007 | BJ | | | | D04326J | 43 | | | 162-199 |
| 106 | 22 | | PA | 2-9 | 33-25-11 | D04326J | 8 | | | | | | TB0174D | A021 | 2 | | 050-099, 150-199 |
| 107 | 22 | | PA | 2-9 | 33-25-11 | D04326J | 5 | | | | | | TB0174D | C021 | 2 | | 050-099, 150-199 |
| 118 | 22 | | PA | 4-11 | 21-66-31 | D04282J | 10 | | | | | | TB0146Y | C044 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1102 | 286T1102 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 118 | 22 | | PA | | 4-11 | 21-66-31 | D04282J | | | | TB0146Y | C044 | BJ | | 150, 152-199 |
| 119 | 22 | | PA | | 4-11 | 21-66-31 | D04282J | | | 13 | TB0146Y | C044 | BJ | | 050-099, 150, 152-199 |
| 120 | 22 | | PA | | 5-0 | 21-66-31 | D04282J | | | 14 | TB0146Y | A045 | BJ | | 050-099, 150, 152-199 |
| 201B | 22 | | PB | A | 2-9 | 23-31-14 | D04326J | | | 10 | TB0174Z | | 24 | BJ | ALL |
| 201R | 22 | | PB | A | 0-0 | 23-31-14 | D04326J | | | 9 | TB0174Z | | 23 | BJ | ALL |
| 202B | 22 | | PB | B | 3-0 | 23-31-14 | D04326J | | | 12 | TB0174Z | | 34 | BJ | 050-099 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-14 | TB0174Z | | | 34 | D04326J | | 12 | | 150-199 |
| 202R | 22 | | PB | B | 0-0 | 23-31-14 | D04326J | | | 11 | TB0174Z | | 33 | BJ | 050-099 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-14 | TB0174Z | | | 33 | D04326J | | 11 | | 150-199 |
| 608 | 22 | | PA | | 2-6 | 33-25-11 | D04326J | | | 14 | TB0146X | C010 | BJ | | 050-099, 150-199 |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L | | | | | | | | | | | |
| 001 | 24 | | PK | | 4-0 | 34-22-14 | D05097P | | | 25 | TB0130G | | 14 | 2 | 050-099, 280-299 |
| 001 | 24 | | PK | | 3-0 | 34-22-14 | D05097P | | | 25 | TB0130G | | 14 | 2 | 150-199, 275-278 |
| 002 | 24 | | PK | | 4-0 | 34-22-14 | D05097P | | | 27 | TB0130Y | A015 | BJ | | 050-099, 280-299 |
| 002 | 24 | | PK | | 3-0 | 34-22-14 | D05097P | | | 27 | TB0130G | | 15 | 2 | 150-154, 275-276 |
| 002 | 24 | | PK | | 3-0 | 34-22-14 | D05097P | | | 27 | TB0130Y | A015 | BJ | | 155-199, 277-278 |
| 003 | 24 | | PK | | 4-0 | 34-22-14 | D05097P | | | 28 | TB0130Y | C015 | BJ | | 050-099, 280-299 |
| 003 | 24 | | PK | | 3-0 | 34-22-14 | D05097P | | | 28 | TB0130G | | 16 | 2 | 150-154, 275-276 |
| 003 | 24 | | PK | | 3-0 | 34-22-14 | D05097P | | | 28 | TB0130Y | C015 | BJ | | 155-199, 277-278 |
| 005 | 24 | | PK | | 4-0 | 34-22-15 | D05101P | | | 25 | TB0130Y | A016 | BJ | | 050-099, 280-299 |
| 005 | 24 | | PK | | 3-4 | 34-22-15 | D05101P | | | 25 | TB0130G | | 17 | 2 | 150-152, 275-276 |
| 005 | 24 | | PK | | 3-4 | 34-22-15 | D05101P | | | 25 | TB0130Y | A018 | BJ | | 153-154 |
| 005 | 24 | | PK | | 3-3 | 34-22-15 | D05101P | | | 25 | TB0130Y | A016 | BJ | | 155-199, 277-278 |
| 006 | 24 | | PK | | 4-0 | 34-22-15 | D05101P | | | 27 | TB0130Y | C016 | BJ | | 050-099, 280-299 |
| 006 | 24 | | PK | | 3-4 | 34-22-15 | D05101P | | | 27 | TB0130G | | 18 | 2 | 150-152, 275-276 |
| 006 | 24 | | PK | | 3-4 | 34-22-15 | D05101P | | | 27 | TB0130Y | C018 | BJ | | 153-154 |
| 006 | 24 | | PK | | 3-3 | 34-22-15 | D05101P | | | 27 | TB0130Y | C016 | BJ | | 155-199, 277-278 |
| 007 | 24 | | PK | | 4-0 | 34-22-15 | D05101P | | | 28 | TB0130G | | 19 | 2 | 050-099, 280-299 |
| 007 | 24 | | PK | | 3-4 | 34-22-15 | D05101P | | | 28 | TB0130G | | 19 | 2 | 150-199, 275-278 |
| 008 | 24 | | PK | | 4-0 | 34-22-17 | D00425A | | | E11 | TB0130H | | 1 | 2 | 050-099, 280-299 |
| 008 | 24 | | PK | | 2-6 | 34-22-17 | D00425A | | | E11 | TB0130H | | 1 | 2 | 150-199, 275-278 |
| 009 | 24 | | PK | | 4-0 | 34-22-17 | D00425A | | | G11 | TB0130H | | 3 | 2 | 050-099, 280-299 |
| 009 | 24 | | PK | | 2-6 | 34-22-17 | D00425A | | | G11 | TB0130H | | 3 | 2 | 150-199, 275-278 |
| 010 | 24 | | PK | | 4-0 | 34-22-17 | D00425A | | | J12 | TB0130G | | 29 | 2 | 050-099, 280-299 |
| 010 | 24 | | PK | | 3-2 | 34-22-17 | D00425A | | | J12 | TB0130G | | 29 | 2 | 150-199, 275-278 |
| 011 | 24 | | PK | | 4-0 | 34-22-17 | D00425A | | | K12 | TB0130G | | 30 | 2 | 050-099, 280-299 |
| 011 | 24 | | PK | | 3-2 | 34-22-17 | D00425A | | | K12 | TB0130G | | 30 | 2 | 150-199, 275-278 |
| 012 | 24 | | PK | | 3-0 | 34-22-16 | D00425C | | | 1 | D04281P | | 2 | | 050-099, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | | |
| 012 | 24 | | PK | | 2-3 | 34-22-16 | D00425C | | 1 | | | | D04281P | 2 | | 150-199, 275-278 |
| 013 | 20 | | PA | | 3-0 | 34-22-16 | D00425C | | 4 | | | | GDX0003 | A.. | 2 | 050-099, 280-299 |
| 013 | 20 | | PA | | 1-11 | 34-22-16 | D00425C | | 4 | | | | GDX0003 | A.. | 2 | 150-199, 275-278 |
| 014 | 20 | | PA | | 3-0 | 34-22-16 | D00425C | | 6 | | | | GDX0003 | S.. | 2 | 050-099, 280-299 |
| 014 | 20 | | PA | | 1-11 | 34-22-16 | D00425C | | 6 | | | | GDX0003 | S.. | 2 | 150-199, 275-278 |
| 015 | 22 | | PA | | 3-0 | 34-22-16 | D00425B | | G08 | | | | GDX0003 | S.. | 2 | 050-099, 280-299 |
| 015 | 22 | | PA | | 1-11 | 34-22-16 | D00425B | | G08 | | | | GDX0003 | S.. | 2 | 150-199, 275-278 |
| 016 | 22 | | PA | | 3-0 | 34-31-11 | D00425A | | E12 | | | | D05603J | 46 | | 050-099, 280-299 |
| 016 | 22 | | PA | | 2-0 | 34-31-11 | D00425A | | E12 | | | | D05603J | 46 | | 150-199, 275-278 |
| 017 | 24 | | PK | | 4-0 | 34-46-12 | D00425E | | A11 | | | | D05205P | 6 | | 050-099 |
| 017 | 24 | | PK | | 2-11 | 34-46-12 | D00425E | | A11 | | | | D05205P | 6 | | 150-199, 275-278 |
| 018 | 24 | | PK | | 4-0 | 33-16-14 | D00425D | | B12 | | | | TB0130G | 11 | 2 | 050-099, 280-299 |
| 018 | 24 | | PK | | 2-6 | 33-16-14 | D00425D | | B12 | | | | TB0130G | 11 | 2 | 150-199, 275-278 |
| 019 | 24 | | PK | | 3-0 | 34-22-14 | TB0130G | | 14 | 2 | | | D00425A | A09 | | 050-099, 280-299 |
| 019 | 24 | | PK | | 2-4 | 34-22-14 | TB0130G | | 14 | 2 | | | D00425A | A09 | | 150-199, 275-278 |
| 020 | 24 | | PK | | 3-0 | 34-22-14 | TB0130Y | | A015 | BJ | | | D00425A | B09 | | 050-099, 280-299 |
| 020 | 24 | | PK | | 2-4 | 34-22-14 | TB0130G | | 15 | 2 | | | D00425A | B09 | | 150-154, 275-276 |
| 020 | 24 | | PK | | 2-4 | 34-22-14 | TB0130Y | | A015 | BJ | | | D00425A | B09 | | 155-199, 277-278 |
| 021 | 24 | | PK | | 3-0 | 34-22-14 | TB0130Y | | C015 | BJ | | | D00425A | C09 | | 050-099, 280-299 |
| 021 | 24 | | PK | | 2-4 | 34-22-14 | TB0130G | | 16 | 2 | | | D00425A | C09 | | 150-154, 275-276 |
| 021 | 24 | | PK | | 2-4 | 34-22-14 | TB0130Y | | C015 | BJ | | | D00425A | C09 | | 155-199, 277-278 |
| 022 | 24 | | PK | | 3-0 | 34-22-14 | TB0130Y | | A016 | BJ | | | D00425D | F09 | | 050-099, 280-299 |
| 022 | 24 | | PK | | 2-5 | 34-22-14 | TB0130G | | 17 | 2 | | | D00425D | F09 | | 150-152, 275-276 |
| 022 | 24 | | PK | | 2-5 | 34-22-14 | TB0130Y | | A018 | BJ | | | D00425D | F09 | | 153-154 |
| 022 | 24 | | PK | | 2-4 | 34-22-14 | TB0130Y | | A016 | BJ | | | D00425D | F09 | | 155-199, 277-278 |
| 023 | 24 | | PK | | 3-0 | 34-22-14 | TB0130Y | | C016 | BJ | | | D00425D | G09 | | 050-099, 280-299 |
| 023 | 24 | | PK | | 2-5 | 34-22-14 | TB0130G | | 18 | 2 | | | D00425D | G09 | | 150-152, 275-276 |
| 023 | 24 | | PK | | 2-5 | 34-22-14 | TB0130Y | | C018 | BJ | | | D00425D | G09 | | 153-154 |
| 023 | 24 | | PK | | 2-4 | 34-22-14 | TB0130Y | | C016 | BJ | | | D00425D | G09 | | 155-199, 277-278 |
| 024 | 24 | | PK | | 3-0 | 34-22-14 | TB0130G | | 19 | 2 | | | D00425D | H09 | | 050-099, 280-299 |
| 024 | 24 | | PK | | 2-5 | 34-22-14 | TB0130G | | 19 | 2 | | | D00425D | H09 | | 150-199, 275-278 |
| 025 | 24 | | PK | | 3-0 | 34-22-15 | TB0130Y | | A016 | BJ | | | D00425A | F09 | | 050-099, 280-299 |
| 025 | 24 | | PK | | 2-5 | 34-22-15 | TB0130G | | 17 | 2 | | | D00425A | F09 | | 150-152, 275-276 |
| 025 | 24 | | PK | | 2-5 | 34-22-15 | TB0130Y | | A018 | BJ | | | D00425A | F09 | | 153-154 |
| 025 | 24 | | PK | | 2-4 | 34-22-15 | TB0130Y | | A016 | BJ | | | D00425A | F09 | | 155-199, 277-278 |
| 026 | 24 | | PK | | 3-0 | 34-22-15 | TB0130Y | | C016 | BJ | | | D00425A | G09 | | 050-099, 280-299 |
| 026 | 24 | | PK | | 2-5 | 34-22-15 | TB0130G | | 18 | 2 | | | D00425A | G09 | | 150-152, 275-276 |
| 026 | 24 | | PK | | 2-5 | 34-22-15 | TB0130Y | | C018 | BJ | | | D00425A | G09 | | 153-154 |
| 026 | 24 | | PK | | 2-4 | 34-22-15 | TB0130Y | | C016 | BJ | | | D00425A | G09 | | 155-199, 277-278 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | | |
| 027 | 24 | | PK | 3-0 | 34-22-15 | TB0130G | 19 | 2 | | D00425A | H09 | | | 050-099, 280-299 | | |
| 027 | 24 | | PK | 2-5 | 34-22-15 | TB0130G | 19 | 2 | | D00425A | H09 | | | 150-199, 275-278 | | |
| 028 | 24 | | PK | 3-0 | 34-22-14 | TB0130Y | C015 | BJ | | D00425D | C09 | | | 050-099, 280-299 | | |
| 028 | 24 | | PK | 2-4 | 34-22-14 | TB0130G | 16 | 2 | | D00425D | C09 | | | 150-154, 275-276 | | |
| 028 | 24 | | PK | 2-4 | 34-22-14 | TB0130Y | C015 | BJ | | D00425D | C09 | | | 155-199, 277-278 | | |
| 029 | 24 | | PK | 3-0 | 34-22-14 | TB0130Y | A015 | BJ | | D00425D | B09 | | | 050-099, 280-299 | | |
| 029 | 24 | | PK | 2-4 | 34-22-14 | TB0130G | 15 | 2 | | D00425D | B09 | | | 150-154, 275-276 | | |
| 029 | 24 | | PK | 2-4 | 34-22-14 | TB0130Y | A015 | BJ | | D00425D | B09 | | | 155-199, 277-278 | | |
| 030 | 24 | | PK | 3-0 | 34-22-14 | TB0130G | 14 | 2 | | D00425D | A09 | | | 050-099, 280-299 | | |
| 030 | 24 | | PK | 2-4 | 34-22-14 | TB0130G | 14 | 2 | | D00425D | A09 | | | 150-199, 275-278 | | |
| 031 | 24 | | PK | 4-0 | 34-22-17 | TB0130H | 1 | 2 | | D05581P | 6 | | | 050-099, 280-299 | | |
| 031 | 24 | | PK | 3-3 | 34-22-17 | TB0130H | 1 | 2 | | D05581P | 6 | | | 150-199, 275-278 | | |
| 032 | 24 | | PK | 4-0 | 34-22-17 | TB0130H | 3 | 2 | | D05581P | 2 | | | 050-099, 280-299 | | |
| 032 | 24 | | PK | 3-3 | 34-22-17 | TB0130H | 3 | 2 | | D05581P | 2 | | | 150-199, 275-278 | | |
| 033 | 24 | | PK | 5-0 | 34-22-17 | TB0130G | 29 | 2 | | D05581P | 3 | | | 050-099, 280-299 | | |
| 033 | 24 | | PK | 3-11 | 34-22-17 | TB0130G | 29 | 2 | | D05581P | 3 | | | 150-199, 275-278 | | |
| 034 | 24 | | PK | 5-0 | 34-22-17 | TB0130G | 30 | 2 | | D05581P | 4 | | | 050-099, 280-299 | | |
| 034 | 24 | | PK | 3-11 | 34-22-17 | TB0130G | 30 | 2 | | D05581P | 4 | | | 150-199, 275-278 | | |
| 035 | 24 | | PK | 4-0 | 34-22-37 | D04923P | 1 | | | TB0130G | 29 | 2 | | 050-099, 280-299 | | |
| 035 | 24 | | PK | 3-2 | 34-22-37 | D04923P | 1 | | | TB0130G | 29 | 2 | | 150-199, 275-278 | | |
| 036 | 24 | | PK | 4-0 | 34-22-37 | D04923P | 2 | | | TB0130G | 30 | 2 | | 050-099, 280-299 | | |
| 036 | 24 | | PK | 3-2 | 34-22-37 | D04923P | 2 | | | TB0130G | 30 | 2 | | 150-199, 275-278 | | |
| 037 | 24 | | PK | 5-0 | 34-22-37 | D04923P | 3 | | | TB0130H | 1 | 2 | | 050-099, 280-299 | | |
| 037 | 24 | | PK | 3-10 | 34-22-37 | D04923P | 3 | | | TB0130H | 1 | 2 | | 150-199, 275-278 | | |
| 038 | 24 | | PK | 5-0 | 34-22-37 | D04923P | 4 | | | TB0130H | 3 | 2 | | 050-099, 280-299 | | |
| 038 | 24 | | PK | 3-10 | 34-22-37 | D04923P | 4 | | | TB0130H | 3 | 2 | | 150-199, 275-278 | | |
| 039 | 24 | | PK | 4-0 | 34-43-11 | D04889P | 1 | | | TB0130H | 3 | 2 | | 050-099, 280-299 | | |
| 039 | 24 | | PK | 3-4 | 34-43-11 | D04889P | 1 | | | TB0130H | 3 | 2 | | 150-199, 275-278 | | |
| 040 | 24 | | PK | 5-0 | 31-31-13 | TB0130H | 3 | 2 | | D04923P | 21 | | | 050-099, 280-299 | | |
| 040 | 24 | | PK | 3-10 | 31-31-13 | TB0130H | 3 | 2 | | D04923P | 21 | | | 150-199, 275-278 | | |
| 043 | 24 | | PK | 5-0 | 31-31-13 | D04923P | 23 | | | TB0130F | A090 | 2 | | ALL | | |
| 044 | 24 | | PK | 5-0 | 31-31-13 | D04923P | 24 | | | TB0130F | C090 | 2 | | ALL | | |
| 045 | 24 | | PK | 6-0 | 31-31-13 | D04923P | 25 | | | TB0130G | 182 | 2 | | 050-099, 280-299 | | |
| 045 | 24 | | PK | 4-4 | 31-31-13 | D04923P | 25 | | | TB0130G | 182 | 2 | | 150-199, 275-278 | | |
| 046 | 24 | | PK | 5-0 | 31-31-13 | D04923P | 26 | | | TB0130F | C089 | 2 | | ALL | | |
| 047 | 24 | | PK | 5-0 | 31-31-13 | D04923P | 27 | | | TB0130F | A088 | 2 | | ALL | | |
| 048 | 24 | | PK | 5-0 | 31-31-13 | D04923P | 28 | | | TB0130F | C088 | 2 | | ALL | | |
| 049 | 24 | | PK | 5-0 | 31-31-13 | D04923P | 29 | | | TB0130F | A087 | 2 | | ALL | | |
| 053 | 24 | | PK | 4-0 | 31-31-21 | D04923P | 48 | | | TB0130F | C126 | 2 | | 050-099, 280-299 | | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | | | |
| 053 | 24 | | PK | 3-0 | 31-31-21 | D04923P | | 48 | | | | | TB0130F | C126 | 2 | | 150-199, 275-278 |
| 054 | 24 | | PK | 4-0 | 31-31-21 | D04923P | | 49 | | | | | TB0130F | A127 | 2 | | 050-099, 280-299 |
| 054 | 24 | | PK | 3-0 | 31-31-21 | D04923P | | 49 | | | | | TB0130F | A127 | 2 | | 150-199, 275-278 |
| 056 | 22 | | PA | 3-0 | 34-22-16 | D00425B | | E10 | | | | | GDX0003 | S.. | 2 | | 050-099, 280-299 |
| 056 | 22 | | PA | 1-11 | 34-22-16 | D00425B | | E10 | | | | | GDX0003 | S.. | 2 | | 150-199, 275-278 |
| 060 | 24 | | PK | 5-0 | 22-41-11 | D00745A | | C11 | | | | | D05603J | | 8 | | 050-099, 280-299 |
| 060 | 24 | | PK | 3-10 | 22-41-11 | D00745A | | C11 | | | | | D05603J | | 8 | | 150-199, 275-278 |
| 061 | 22 | | PA | 6-0 | 22-32-12 | D00745A | | E14 | | | | | D05603J | | 12 | | 050-099, 280-299 |
| 061 | 22 | | PA | 3-10 | 22-32-12 | D00745A | | E14 | | | | | D05603J | | 12 | | 150-199, 275-278 |
| 062 | 22 | | PA | 6-0 | 22-41-11 | D00745A | | D04 | | | | | D05603J | | 4 | | 050-099, 280-299 |
| 062 | 22 | | PA | 3-10 | 22-41-11 | D00745A | | D04 | | | | | D05603J | | 4 | | 150-199, 275-278 |
| 063 | 22 | | PQ | 4-0 | 22-41-11 | D00745A | | H04 | | | | | TB0130F | A149 | 2 | | 050-099, 280-299 |
| 063 | 22 | | PQ | 2-11 | 22-41-11 | D00745A | | H04 | | | | | TB0130F | A149 | 2 | | 150-199, 275-278 |
| 063Z | | | CM | 0-0 | 22-41-11 | D00745A | | DED | | | | | TB0130F | DED | | | ALL |
| 064 | 24 | | PK | 5-0 | 22-41-11 | D00745A | | C09 | | | | | D05205P | | 37 | | 050-099, 280-299 |
| 064 | 24 | | PK | 3-7 | 22-41-11 | D00745A | | C09 | | | | | D05205P | | 37 | | 150-199, 275-278 |
| 065 | 20 | | PA | 3-0 | 22-41-11 | D00745C | | 7 | | | | | GDX0008 | D.. | 2 | | 050-099, 280-299 |
| 065 | 20 | | PA | 2-0 | 22-41-11 | D00745C | | 7 | | | | | GDX0008 | D.. | 2 | | 150-199, 275-278 |
| 066 | 20 | | PA | 3-0 | 22-41-11 | D00745C | | 11 | | | | | GDX0008 | D.. | 2 | | 050-099, 280-299 |
| 066 | 20 | | PA | 2-0 | 22-41-11 | D00745C | | 11 | | | | | GDX0008 | D.. | 2 | | 150-199, 275-278 |
| 067 | 24 | | PK | 5-0 | 22-41-11 | D00745A | | C10 | | | | | D04923P | | 50 | | 050-099, 280-299 |
| 067 | 24 | | PK | 3-10 | 22-41-11 | D00745A | | C10 | | | | | D04923P | | 50 | | 150-199, 275-278 |
| 068 | 20 | | PA | 5-0 | 22-41-12 | D00745C | | 3 | | | | | D04281P | | 1 | | 050-099, 280-299 |
| 068 | 20 | | PA | 4-1 | 22-41-12 | D00745C | | 3 | | | | | D04281P | | 1 | | 150-199, 275-278 |
| 069 | 20 | | PA | 3-0 | 22-41-12 | D00745C | | 2 | | | | | GDX0008 | A.. | 2 | | 050-099, 280-299 |
| 069 | 20 | | PA | 2-0 | 22-41-12 | D00745C | | 2 | | | | | GDX0008 | A.. | 2 | | 150-199, 275-278 |
| 070 | 20 | | PA | 3-0 | 22-41-12 | D00745C | | 5 | | | | | GDX0008 | S.. | 2 | | 050-099, 280-299 |
| 070 | 20 | | PA | 2-0 | 22-41-12 | D00745C | | 5 | | | | | GDX0008 | S.. | 2 | | 150-199, 275-278 |
| 073 | 24 | | PK | 4-0 | 34-22-17 | D05581P | | 22 | | | | | D00425A | F12 | | | 050-099, 280-299 |
| 073 | 24 | | PK | 2-7 | 34-22-17 | D05581P | | 22 | | | | | D00425A | F12 | | | 150-199, 275-278 |
| 074 | 22 | | PA | 5-0 | 34-22-16 | TB0130G | | 129 | 2 | | | | D04281P | | 3 | | 050-099, 280-299 |
| 074 | 22 | | PA | 3-7 | 34-22-16 | TB0130G | | 129 | 2 | | | | D04281P | | 3 | | 150-199, 275-278 |
| 075 | 22 | | PA | 4-0 | 34-22-16 | TB0130G | | 5 | 2 | | | | D05581P | | 23 | | 050-099, 280-299 |
| 075 | 22 | | PA | 3-3 | 34-22-16 | TB0130G | | 5 | 2 | | | | D05581P | | 23 | | 150-199, 275-278 |
| 076 | 24 | | PK | 6-0 | 22-41-13 | D00745A | | J14 | | | | | D05867P | | 6 | | 050-099, 280-299 |
| 076 | 24 | | PK | 4-7 | 22-41-13 | D00745A | | J14 | | | | | D05867P | | 6 | | 150-199, 275-278 |
| 077 | 24 | | PK | 6-0 | 22-41-13 | D00745A | | K13 | | | | | D05867P | | 7 | | 050-099, 280-299 |
| 077 | 24 | | PK | 4-7 | 22-41-13 | D00745A | | K13 | | | | | D05867P | | 7 | | 150-199, 275-278 |
| 078 | 24 | | PK | 6-0 | 22-41-13 | D00745A | | J13 | | | | | D05867P | | 8 | | 050-099, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | |
| 078 | 24 | | PK | | 4-7 | 22-41-13 | D00745A | | J13 | | D05867P | | 8 | | 150-199, 275-278 |
| 079 | 24 | | PK | | 6-0 | 22-41-13 | D00745A | | J12 | | D05867P | | 9 | | 050-099, 280-299 |
| 079 | 24 | | PK | | 4-7 | 22-41-13 | D00745A | | J12 | | D05867P | | 9 | | 150-199, 275-278 |
| 080 | 24 | | PK | | 6-0 | 22-41-13 | D00745A | | K12 | | D05867P | | 10 | | 050-099, 280-299 |
| 080 | 24 | | PK | | 4-7 | 22-41-13 | D00745A | | K12 | | D05867P | | 10 | | 150-199, 275-278 |
| 081 | 20 | | PA | | 6-0 | 22-41-13 | D05867P | | 14 | | GD00012 | | D.. | 2 | 050-099, 280-299 |
| 081 | 20 | | PA | | 4-9 | 22-41-13 | D05867P | | 14 | | GD00012 | | D.. | 2 | 150-199, 275-278 |
| 082 | 24 | | PK | | 6-0 | 31-31-19 | D04923P | | 43 | | TB0130D | A196 | 2 | | 050-099, 280-299 |
| 082 | 24 | | PK | | 5-1 | 31-31-19 | D04923P | | 43 | | TB0130D | A196 | 2 | | 150-199, 275-278 |
| 084 | 24 | | PK | | 6-0 | 22-41-13 | D00745A | | K11 | | D05867P | | 4 | | 050-099, 280-299 |
| 084 | 24 | | PK | | 4-7 | 22-41-13 | D00745A | | K11 | | D05867P | | 4 | | 150-199, 275-278 |
| 085 | 24 | | PK | | 6-0 | 22-41-13 | D00745A | | K14 | | D05867P | | 5 | | 050-099, 280-299 |
| 085 | 24 | | PK | | 4-7 | 22-41-13 | D00745A | | K14 | | D05867P | | 5 | | 150-199, 275-278 |
| 086 | 22 | | PA | | 6-0 | 34-46-12 | D05205P | | 44 | | TB0130D | C191 | 2 | | 050-099, 280-299 |
| 086 | 22 | | PA | | 4-9 | 34-46-12 | D05205P | | 44 | | TB0130D | C191 | 2 | | 150-199, 275-278 |
| 088 | 24 | | PK | | 1-0 | 22-41-11 | D00745A | | B14 | | D00745A | B06 | | | 050-099, 280-299 |
| 088 | 24 | | PK | | 0-7 | 22-41-11 | D00745A | | B14 | | D00745A | B06 | | | 150-199, 275-278 |
| 089 | 24 | | PK | | 1-0 | 22-41-11 | D00745A | | H14 | | D00745A | K06 | | | 050-099, 280-299 |
| 089 | 24 | | PK | | 0-7 | 22-41-11 | D00745A | | H14 | | D00745A | K06 | | | 150-199, 275-278 |
| 091 | 22 | | PA | | 3-0 | 34-22-16 | D00425B | | F09 | | GD00003 | S.. | 2 | | 050-099, 280-299 |
| 091 | 22 | | PA | | 1-11 | 34-22-16 | D00425B | | F09 | | GD00003 | S.. | 2 | | 150-199, 275-278 |
| 092 | 22 | | PA | | 3-0 | 34-22-16 | D00425B | | G09 | | GD00003 | S.. | 2 | | 050-099, 280-299 |
| 092 | 22 | | PA | | 1-11 | 34-22-16 | D00425B | | G09 | | GD00003 | S.. | 2 | | 150-199, 275-278 |
| 094 | 22 | | PA | | 4-0 | 34-22-16 | D05603J | | 53 | | D00425B | D08 | | | 050-099, 280-299 |
| 094 | 22 | | PA | | 2-0 | 34-22-16 | D05603J | | 53 | | D00425B | D08 | | | 150-199, 275-278 |
| 095 | 22 | | PA | | 4-0 | 34-22-13 | D00425D | | F13 | | TB0130F | A020 | 2 | | 050-099, 280-299 |
| 095 | 22 | | PA | | 2-5 | 34-22-13 | D00425D | | F13 | | TB0130F | A020 | 2 | | 150-199, 275-278 |
| 097 | 22 | | PA | | 3-0 | 34-22-16 | D00425B | | D10 | | GD00003 | S.. | 2 | | 050-099, 280-299 |
| 097 | 22 | | PA | | 1-11 | 34-22-16 | D00425B | | D10 | | GD00003 | S.. | 2 | | 150-199, 275-278 |
| 098 | 22 | | PA | | 3-0 | 34-22-16 | D00425B | | D12 | | GD00003 | S.. | 2 | | 050-099, 280-299 |
| 098 | 22 | | PA | | 1-11 | 34-22-16 | D00425B | | D12 | | GD00003 | S.. | 2 | | 150-199, 275-278 |
| 099 | 22 | | PA | | 5-0 | 34-22-23 | D05205P | | 47 | | TB0130G | 5 | 2 | | 050-099, 280-299 |
| 099 | 22 | | PA | | 3-7 | 34-22-23 | D05205P | | 47 | | TB0130G | 5 | 2 | | 150-199, 275-278 |
| 102 | 22 | | PA | | 2-0 | 34-22-16 | D00425B | | D11 | | GD00003 | S.. | 2 | | 050-099 |
| 102 | 22 | | PA | | 1-11 | 34-22-16 | D00425B | | D11 | | GD00003 | S.. | 2 | | 150-199, 275-278 |
| 102 | 22 | | PA | | 3-0 | 34-22-16 | D00425B | | D11 | | GD00003 | S.. | 2 | | 280-299 |
| 104 | 24 | | PK | | 4-0 | 34-22-17 | D00425A | | A11 | | TB0130F | A142 | 2 | | 050-099, 280-299 |
| 104 | 24 | | PK | | 3-4 | 34-22-17 | D00425A | | A11 | | TB0130F | A142 | 2 | | 150-199, 275-278 |
| 105 | 24 | | PK | | 4-0 | 34-22-16 | TB0130G | | 128 | 2 | D00425A | K13 | | | 050-099, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | | |
| 105 | 24 | | PK | 3-0 | 34-22-16 | TB0130G | 128 | 2 | | D00425A | K13 | | | 150-199, 275-278 | | |
| 106 | 22 | | PA | 2-0 | 34-22-16 | D00425D | D12 | | | GDX0003 | S.. | 2 | | 050-099 | | |
| 106 | 22 | | PA | 1-11 | 34-22-16 | D00425D | D12 | | | GDX0003 | S.. | 2 | | 150-199, 275-278 | | |
| 106 | 22 | | PA | 3-0 | 34-22-16 | D00425D | D12 | | | GDX0003 | S.. | 2 | | 280-299 | | |
| 109 | 22 | | PA | 3-0 | 34-22-16 | D00425B | D05 | | | GDX0001 | S.. | 2 | | 050-099, 280-299 | | |
| 109 | 22 | | PA | 1-8 | 34-22-16 | D00425B | D05 | | | GDX0001 | S.. | 2 | | 150-199, 275-278 | | |
| 112 | 24 | | PK | 4-0 | 34-22-16 | TB0130G | 128 | 2 | | D00425A | C14 | | | 050-099, 280-299 | | |
| 112 | 24 | | PK | 3-0 | 34-22-16 | TB0130G | 128 | 2 | | D00425A | C14 | | | 150-199, 275-278 | | |
| 115 | 22 | | PA | 1-8 | 34-22-16 | D00425B | K04 | | | GDX0001 | S.. | 2 | | 156-157, 166-199, 277-278 | | |
| 115 | 22 | | PA | 3-0 | 34-22-16 | D00425B | K04 | | | GDX0001 | S.. | 2 | | 280-299 | | |
| 121 | 24 | | PK | 4-0 | 34-22-16 | D05205P | 8 | | | TB0130G | 128 | 2 | | 050-099, 280-299 | | |
| 121 | 24 | | PK | 2-9 | 34-22-16 | D05205P | 8 | | | TB0130G | 128 | 2 | | 150-199, 275-278 | | |
| 123 | 22 | | PA | 3-0 | 34-22-16 | D00425B | F06 | | | GDX0003 | S.. | 2 | | 050-099, 280-299 | | |
| 123 | 22 | | PA | 1-11 | 34-22-16 | D00425B | F06 | | | GDX0003 | S.. | 2 | | 150-199, 275-278 | | |
| 125 | 22 | | PA | 3-0 | 34-22-16 | D00425B | B04 | | | GDX0003 | S.. | 2 | | 050-099, 280-299 | | |
| 125 | 22 | | PA | 1-11 | 34-22-16 | D00425B | B04 | | | GDX0003 | S.. | 2 | | 150-199, 275-278 | | |
| 126 | 22 | | PA | 3-0 | 34-22-16 | D00425B | G06 | | | GDX0003 | S.. | 2 | | 050-099, 280-299 | | |
| 126 | 22 | | PA | 1-11 | 34-22-16 | D00425B | G06 | | | GDX0003 | S.. | 2 | | 150-199, 275-278 | | |
| 128 | 22 | | PA | 4-0 | 34-22-16 | D00425A | D14 | | | D05205P | 55 | | | 050-099, 280-299 | | |
| 128 | 22 | | PA | 2-11 | 34-22-16 | D00425A | D14 | | | D05205P | 55 | | | 150-199, 275-278 | | |
| 136 | 22 | | PA | 3-0 | 34-22-16 | D00425B | J05 | | | GDX0003 | S.. | 2 | | 050-099, 280-299 | | |
| 136 | 22 | | PA | 1-11 | 34-22-16 | D00425B | J05 | | | GDX0003 | S.. | 2 | | 150-199, 275-278 | | |
| 139 | 22 | | PA | 2-6 | 34-22-16 | D00425F | 4 | | | TB0130G | 5 | 2 | | ALL | | |
| 144 | 24 | | PK | 1-0 | 22-41-11 | D00745A | F06 | | | D00745A | H15 | | | 050-099, 280-299 | | |
| 144 | 24 | | PK | 0-7 | 22-41-11 | D00745A | F06 | | | D00745A | H15 | | | 150-199, 275-278 | | |
| 145 | 22 | | PA | 4-0 | 31-31-22 | TB0130X | B132 | BJ | | D05223P | 6 | | | 050-099, 275-276, 280-299 | | |
| 145 | 22 | | PA | 3-4 | 31-31-22 | TB0130X | B132 | BJ | | D05223P | 6 | | | 150-199, 277-278 | | |
| 146 | 24 | | PK | 5-0 | 31-31-22 | D05223P | 11 | | | TB0130X | D050 | BJ | | 050-099, 275-276, 280-299 | | |
| 146 | 24 | | PK | 3-10 | 31-31-22 | D05223P | 11 | | | TB0130X | D050 | BJ | | 150-199, 277-278 | | |
| 148 | 22 | | PA | 4-0 | 34-22-16 | D00425F | 1 | | | TB0130G | 129 | 2 | | 050-099, 280-299 | | |
| 148 | 22 | | PA | 3-1 | 34-22-16 | D00425F | 1 | | | TB0130G | 129 | 2 | | 150-199, 275-278 | | |
| 149 | 24 | | PK | 5-0 | 34-22-38 | D05223P | 10 | | | TB0130G | 129 | 2 | | 050-099, 275-276, 280-299 | | |
| 149 | 24 | | PK | 3-3 | 34-22-38 | D05223P | 10 | | | TB0130G | 129 | 2 | | 150-199, 277-278 | | |
| 151 | 24 | | PK | 5-0 | 34-61-25 | D04923P | 12 | | | TB0130H | 1 | 2 | | 050-099, 280-299 | | |
| 151 | 24 | | PK | 3-10 | 34-61-25 | D04923P | 12 | | | TB0130H | 1 | 2 | | 150-199, 275-278 | | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | |
| 201B | 24 | PW | IA | | 4-0 | 34-22-14 | TB0130H | 25 | 2 | | D00425A | F05 | | | 050-099, 280-299 |
| 201B | 24 | PW | IA | | 3-1 | 34-22-14 | TB0130H | 25 | 2 | | D00425A | F05 | | | 150-199, 275-278 |
| 201R | 24 | PW | IA | | 0-0 | 34-22-14 | TB0130H | 23 | 2 | | D00425A | E05 | | | ALL |
| 201Z | | | | | 0-0 | 34-22-14 | GDY0005 | S.. | 2 | | D00425A | DED | | | ALL |
| 202W | 26 | BW | IB | | 3-0 | 34-22-14 | D05097P | | 2 | | D00425E | B01 | | | 050-099, 280-299 |
| 202W | 26 | BW | IB | | 2-5 | 34-22-14 | D05097P | | 2 | | D00425E | B01 | | | 150-199, 275-278 |
| 202WN | 26 | BW | IB | | 0-0 | 34-22-14 | D05097P | | 1 | | D00425E | A01 | | | ALL |
| 202Z | | | | | 0-0 | 34-22-14 | D05097P | 19 | | | GDZ0002 | S.. | 2 | | ALL |
| 203W | 26 | BW | IC | | 3-0 | 34-22-14 | D05097P | | 4 | | D00425E | B02 | | | 050-099, 280-299 |
| 203W | 26 | BW | IC | | 2-5 | 34-22-14 | D05097P | | 4 | | D00425E | B02 | | | 150-199, 275-278 |
| 203WN | 26 | BW | IC | | 0-0 | 34-22-14 | D05097P | | 3 | | D00425E | A02 | | | ALL |
| 203Z | | | | | 0-0 | 34-22-14 | D05097P | 20 | | | GDZ0002 | S.. | 2 | | ALL |
| 204W | 26 | BW | ID | | 3-0 | 34-22-14 | D05097P | | 6 | | D00425E | B03 | | | 050-099, 280-299 |
| 204W | 26 | BW | ID | | 2-5 | 34-22-14 | D05097P | | 6 | | D00425E | B03 | | | 150-199, 275-278 |
| 204WN | 26 | BW | ID | | 0-0 | 34-22-14 | D05097P | | 5 | | D00425E | A03 | | | ALL |
| 204Z | | | | | 0-0 | 34-22-14 | D05097P | 21 | | | GDZ0002 | S.. | 2 | | ALL |
| 205W | 26 | BW | IE | | 3-0 | 34-22-14 | D05097P | | 8 | | D00425E | B04 | | | 050-099, 280-299 |
| 205W | 26 | BW | IE | | 2-5 | 34-22-14 | D05097P | | 8 | | D00425E | B04 | | | 150-199, 275-278 |
| 205WN | 26 | BW | IE | | 0-0 | 34-22-14 | D05097P | | 7 | | D00425E | A04 | | | ALL |
| 205Z | | | | | 0-0 | 34-22-14 | D05097P | 22 | | | GDZ0002 | S.. | 2 | | ALL |
| 206W | 26 | BW | IF | | 3-0 | 34-22-14 | D05097P | | 10 | | D00425E | B05 | | | 050-099, 280-299 |
| 206W | 26 | BW | IF | | 2-5 | 34-22-14 | D05097P | | 10 | | D00425E | B05 | | | 150-199, 275-278 |
| 206WN | 26 | BW | IF | | 0-0 | 34-22-14 | D05097P | | 9 | | D00425E | A05 | | | ALL |
| 206Z | | | | | 0-0 | 34-22-14 | D05097P | 23 | | | GDZ0002 | S.. | 2 | | ALL |
| 207W | 26 | BW | IG | | 3-0 | 34-22-14 | D05097P | | 12 | | D00425E | B06 | | | 050-099, 280-299 |
| 207W | 26 | BW | IG | | 2-5 | 34-22-14 | D05097P | | 12 | | D00425E | B06 | | | 150-199, 275-278 |
| 207WN | 26 | BW | IG | | 0-0 | 34-22-14 | D05097P | | 11 | | D00425E | A06 | | | ALL |
| 207Z | | | | | 0-0 | 34-22-14 | D05097P | 29 | | | GDZ0003 | S.. | 2 | | ALL |
| 208W | 26 | BW | IH | | 3-0 | 34-22-14 | D05097P | | 14 | | D00425E | B07 | | | 050-099, 280-299 |
| 208W | 26 | BW | IH | | 2-5 | 34-22-14 | D05097P | | 14 | | D00425E | B07 | | | 150-199, 275-278 |
| 208WN | 26 | BW | IH | | 0-0 | 34-22-14 | D05097P | | 13 | | D00425E | A07 | | | ALL |
| 208Z | | | | | 0-0 | 34-22-14 | D05097P | 30 | | | GDZ0003 | S.. | 2 | | ALL |
| 209W | 26 | BW | II | | 3-0 | 34-22-14 | D05097P | | 16 | | D00425E | B08 | | | 050-099, 280-299 |
| 209W | 26 | BW | II | | 2-5 | 34-22-14 | D05097P | | 16 | | D00425E | B08 | | | 150-199, 275-278 |
| 209WN | 26 | BW | II | | 0-0 | 34-22-14 | D05097P | | 15 | | D00425E | A08 | | | ALL |
| 209Z | | | | | 0-0 | 34-22-14 | D05097P | 31 | | | GDZ0003 | S.. | 2 | | ALL |
| 210W | 26 | BW | IJ | | 3-0 | 34-22-14 | D05097P | | 18 | | D00425E | B09 | | | 050-099, 280-299 |
| 210W | 26 | BW | IJ | | 2-5 | 34-22-14 | D05097P | | 18 | | D00425E | B09 | | | 150-199, 275-278 |
| 210WN | 26 | BW | IJ | | 0-0 | 34-22-14 | D05097P | | 17 | | D00425E | A09 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | |
| 210Z | | | IJ | 0-0 | 34-22-14 | D05097P | | 35 | | GDZ0003 | S.. | 2 | | ALL | |
| 211W | 26 | BW | IK | 3-0 | 34-22-15 | D05101P | | 2 | | D00425E | D01 | | | 050-099, 280-299 | |
| 211W | 26 | BW | IK | 2-8 | 34-22-15 | D05101P | | 2 | | D00425E | D01 | | | 150-199, 275-278 | |
| 211WN | 26 | BW | IK | 0-0 | 34-22-15 | D05101P | | 1 | | D00425E | C01 | | | ALL | |
| 211Z | | | IK | 0-0 | 34-22-15 | D05101P | | 19 | | GDZ0002 | S.. | 2 | | ALL | |
| 212W | 26 | BW | IL | 3-0 | 34-22-15 | D05101P | | 4 | | D00425E | D02 | | | 050-099, 280-299 | |
| 212W | 26 | BW | IL | 2-8 | 34-22-15 | D05101P | | 4 | | D00425E | D02 | | | 150-199, 275-278 | |
| 212WN | 26 | BW | IL | 0-0 | 34-22-15 | D05101P | | 3 | | D00425E | C02 | | | ALL | |
| 212Z | | | IL | 0-0 | 34-22-15 | D05101P | | 20 | | GDZ0002 | S.. | 2 | | ALL | |
| 213W | 26 | BW | IM | 3-0 | 34-22-15 | D05101P | | 6 | | D00425E | D03 | | | 050-099, 280-299 | |
| 213W | 26 | BW | IM | 2-8 | 34-22-15 | D05101P | | 6 | | D00425E | D03 | | | 150-199, 275-278 | |
| 213WN | 26 | BW | IM | 0-0 | 34-22-15 | D05101P | | 5 | | D00425E | C03 | | | ALL | |
| 213Z | | | IM | 0-0 | 34-22-15 | D05101P | | 21 | | GDZ0002 | S.. | 2 | | ALL | |
| 214W | 26 | BW | IN | 3-0 | 34-22-15 | D05101P | | 8 | | D00425E | D04 | | | 050-099, 280-299 | |
| 214W | 26 | BW | IN | 2-8 | 34-22-15 | D05101P | | 8 | | D00425E | D04 | | | 150-199, 275-278 | |
| 214WN | 26 | BW | IN | 0-0 | 34-22-15 | D05101P | | 7 | | D00425E | C04 | | | ALL | |
| 214Z | | | IN | 0-0 | 34-22-15 | D05101P | | 22 | | GDZ0002 | S.. | 2 | | ALL | |
| 215W | 26 | BW | IO | 3-0 | 34-22-15 | D05101P | | 10 | | D00425E | D05 | | | 050-099, 280-299 | |
| 215W | 26 | BW | IO | 2-8 | 34-22-15 | D05101P | | 10 | | D00425E | D05 | | | 150-199, 275-278 | |
| 215WN | 26 | BW | IO | 0-0 | 34-22-15 | D05101P | | 9 | | D00425E | C05 | | | ALL | |
| 215Z | | | IO | 0-0 | 34-22-15 | D05101P | | 23 | | GDZ0002 | S.. | 2 | | ALL | |
| 216W | 26 | BW | IP | 3-0 | 34-22-15 | D05101P | | 12 | | D00425E | D06 | | | 050-099, 280-299 | |
| 216W | 26 | BW | IP | 2-8 | 34-22-15 | D05101P | | 12 | | D00425E | D06 | | | 150-199, 275-278 | |
| 216WN | 26 | BW | IP | 0-0 | 34-22-15 | D05101P | | 11 | | D00425E | C06 | | | ALL | |
| 216Z | | | IP | 0-0 | 34-22-15 | D05101P | | 29 | | GDZ0002 | S.. | 2 | | ALL | |
| 217W | 26 | BW | IQ | 3-0 | 34-22-15 | D05101P | | 14 | | D00425E | D07 | | | 050-099, 280-299 | |
| 217W | 26 | BW | IQ | 2-8 | 34-22-15 | D05101P | | 14 | | D00425E | D07 | | | 150-199, 275-278 | |
| 217WN | 26 | BW | IQ | 0-0 | 34-22-15 | D05101P | | 13 | | D00425E | C07 | | | ALL | |
| 217Z | | | IQ | 0-0 | 34-22-15 | D05101P | | 30 | | GDZ0003 | S.. | 2 | | ALL | |
| 218W | 26 | BW | IR | 3-0 | 34-22-15 | D05101P | | 16 | | D00425E | D08 | | | 050-099, 280-299 | |
| 218W | 26 | BW | IR | 2-8 | 34-22-15 | D05101P | | 16 | | D00425E | D08 | | | 150-199, 275-278 | |
| 218WN | 26 | BW | IR | 0-0 | 34-22-15 | D05101P | | 15 | | D00425E | C08 | | | ALL | |
| 218Z | | | IR | 0-0 | 34-22-15 | D05101P | | 31 | | GDZ0003 | S.. | 2 | | ALL | |
| 219W | 26 | BW | IS | 3-0 | 34-22-15 | D05101P | | 18 | | D00425E | D09 | | | 050-099, 280-299 | |
| 219W | 26 | BW | IS | 2-8 | 34-22-15 | D05101P | | 18 | | D00425E | D09 | | | 150-199, 275-278 | |
| 219WN | 26 | BW | IS | 0-0 | 34-22-15 | D05101P | | 17 | | D00425E | C09 | | | ALL | |
| 219Z | | | IS | 0-0 | 34-22-15 | D05101P | | 35 | | GDZ0003 | S.. | 2 | | ALL | |
| 220B | 24 | PW | IT | 4-0 | 34-22-18 | D00425A | | B03 | | TB0130H | 113 | 2 | | 050-099, 280-299 | |
| 220B | 24 | PW | IT | 2-5 | 34-22-18 | D00425A | | B03 | | TB0130H | 113 | 2 | | 150-199, 275-278 | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 17

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | |
| 220R | 24 | | PW | IT | 0-0 | 34-22-18 | D00425A | A03 | | | TB0130H | 111 | 2 | | ALL |
| 220Z | | | | IT | 0-0 | 34-22-18 | D00425A | DED | | | GDY0002 | S.. | 2 | | ALL |
| 221B | 24 | | PW | IU | 5-0 | 34-22-18 | D00425B | B05 | | | TB0130F | C144 | 2 | | 050-099, 280-299 |
| 221B | 24 | | PW | IU | 3-5 | 34-22-18 | D00425B | B05 | | | TB0130F | C144 | 2 | | 150-199, 275-278 |
| 221R | 24 | | PW | IU | 0-0 | 34-22-18 | D00425B | A05 | | | TB0130F | A144 | 2 | | ALL |
| 221Z | | | | IU | 0-0 | 34-22-18 | D00425B | DED | | | GDY0007 | S.. | 2 | | 050-099 |
| 221Z | | | | IU | 0-0 | 34-22-18 | D00425B | DED | | | GDY0008 | S.. | 2 | | 150-199, 275-299 |
| 222B | 24 | | PW | IV | 5-0 | 34-22-18 | D00425A | B05 | | | TB0130G | 155 | 2 | | 050-099, 280-299 |
| 222B | 24 | | PW | IV | 3-8 | 34-22-18 | D00425A | B05 | | | TB0130G | 155 | 2 | | 150-199, 275-278 |
| 222R | 24 | | PW | IV | 0-0 | 34-22-18 | D00425A | A05 | | | TB0130G | 154 | 2 | | ALL |
| 222Z | | | | IV | 0-0 | 34-22-18 | D00425A | DED | | | GDY0008 | S.. | 2 | | 050-099 |
| 222Z | | | | IV | 0-0 | 34-22-18 | D00425A | DED | | | GDY0009 | S.. | 2 | | 150-199, 275-299 |
| 223B | 24 | | PW | IW | 5-0 | 34-61-16 | D00425D | B03 | | | TB0130Y | C159 | BJ | | 050-099, 280-299 |
| 223B | 24 | | PW | IW | 3-10 | 34-61-16 | D00425D | B03 | | | TB0130Y | C159 | BJ | | 150-199, 275-278 |
| 223R | 24 | | PW | IW | 0-0 | 34-61-16 | D00425D | A03 | | | TB0130Y | A159 | BJ | | ALL |
| 223Z | | | | IW | 0-0 | 34-61-16 | D00425D | DED | | | GDY0009 | S.. | 2 | | ALL |
| 224B | 24 | | PW | IX | 4-0 | 34-22-19 | D00425A | K03 | | | TB0130G | 13 | 2 | | 050-099, 280-299 |
| 224B | 24 | | PW | IX | 2-6 | 34-22-19 | D00425A | K03 | | | TB0130G | 13 | 2 | | 150-199, 275-278 |
| 224R | 24 | | PW | IX | 0-0 | 34-22-19 | D00425A | J03 | | | TB0130G | 12 | 2 | | ALL |
| 224Z | | | | IX | 0-0 | 34-22-19 | D00425A | DED | | | GDY0002 | S.. | 2 | | ALL |
| 225B | 24 | | PW | IY | 4-0 | 34-22-19 | D00425A | H02 | | | TB0130G | 22 | 2 | | 050-099, 280-299 |
| 225B | 24 | | PW | IY | 3-1 | 34-22-19 | D00425A | H02 | | | TB0130G | 22 | 2 | | 150-199, 275-278 |
| 225R | 24 | | PW | IY | 0-0 | 34-22-19 | D00425A | G02 | | | TB0130G | 21 | 2 | | ALL |
| 225Z | | | | IY | 0-0 | 34-22-19 | D00425A | DED | | | GDY0005 | S.. | 2 | | ALL |
| 227 | 20 | | UA | | 1-6 | 34-22-19 | D00425A | REF | | JB | GDY0001 | S.. | 2 | | ALL |
| 227B | 24 | | PW | JB | 3-0 | 34-22-19 | D00425A | D04 | | | D05603J | 30 | | | 050-099, 280-299 |
| 227B | 24 | | PW | JB | 2-0 | 34-22-19 | D00425A | D04 | | | D05603J | 30 | | | 150-199, 275-278 |
| 227R | 24 | | PW | JB | 0-0 | 34-22-19 | D00425A | C04 | | | D05603J | 29 | | | ALL |
| 227Z | | | | JB | 0-0 | 34-22-19 | D00425A | REF | | JB | D05603J | 31 | | | ALL |
| 228 | 20 | | UA | | 1-6 | 34-22-19 | D00425A | REF | | JC | GDY0001 | S.. | 2 | | ALL |
| 228B | 24 | | PW | JC | 3-0 | 34-22-19 | D00425A | K05 | | | D05603J | 33 | | | 050-099, 280-299 |
| 228B | 24 | | PW | JC | 2-0 | 34-22-19 | D00425A | K05 | | | D05603J | 33 | | | 150-199, 275-278 |
| 228R | 24 | | PW | JC | 0-0 | 34-22-19 | D00425A | J05 | | | D05603J | 32 | | | ALL |
| 228Z | | | | JC | 0-0 | 34-22-19 | D00425A | REF | | JC | D05603J | 34 | | | ALL |
| 229B | 24 | | PW | JD | 4-0 | 34-22-19 | D00425B | H04 | | | TB0130H | 123 | 2 | | 050-099, 280-299 |
| 229B | 24 | | PW | JD | 2-11 | 34-22-19 | D00425B | H04 | | | TB0130H | 123 | 2 | | 150-199, 275-278 |
| 229R | 24 | | PW | JD | 0-0 | 34-22-19 | D00425B | G04 | | | TB0130H | 121 | 2 | | ALL |
| 229Z | | | | JD | 0-0 | 34-22-19 | D00425B | DED | | | GDY0005 | S.. | 2 | | ALL |
| 230B | 24 | | PW | JE | 4-0 | 22-41-13 | D05603J | 36 | | | TB0130G | 110 | 2 | | 050-099, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 18

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | | |
| 230B | 24 | PW | JE | 2-7 | 22-41-13 | D05603J | | 36 | | | | TB0130G | 110 | 2 | 150-199, 275-278 | |
| 230R | 24 | PW | JE | 0-0 | 22-41-13 | D05603J | | 35 | | | | TB0130G | 109 | 2 | ALL | |
| 230Z | | | JE | 0-0 | 22-41-13 | D05603J | | 37 | | | | GDY0002 | S.. | 2 | 050-099, 150-154, 275-276 | |
| 230Z | | | JE | 0-0 | 22-41-13 | D05603J | | 37 | | | | GDY0001 | S.. | 2 | 155-199, 277-299 | |
| 231B | 24 | PW | JF | 4-0 | 22-41-13 | D05867P | | 2 | | | | TB0130G | 110 | 2 | 050-099, 280-299 | |
| 231B | 24 | PW | JF | 3-2 | 22-41-13 | D05867P | | 2 | | | | TB0130G | 110 | 2 | 150-199, 275-278 | |
| 231R | 24 | PW | JF | 0-0 | 22-41-13 | D05867P | | 1 | | | | TB0130G | 109 | 2 | ALL | |
| 231Z | | | JF | 0-0 | 22-41-13 | D05867P | | 3 | | | | GDY0002 | S.. | 2 | 050-099, 150-154, 275-276 | |
| 231Z | | | JF | 0-0 | 22-41-13 | D05867P | | 3 | | | | GDY0001 | S.. | 2 | 155-199, 277-299 | |
| 233 | 20 | UA | | 1-6 | 34-22-19 | D00425A | | | | JH | | GDX0001 | S.. | 2 | ALL | |
| 233B | 24 | PW | JH | 4-0 | 34-22-19 | D05205P | | 53 | | | | D00425A | B07 | | 050-099, 280-299 | |
| 233B | 24 | PW | JH | 2-11 | 34-22-19 | D05205P | | 53 | | | | D00425A | B07 | | 150-199, 275-278 | |
| 233R | 24 | PW | JH | 0-0 | 34-22-19 | D05205P | | 52 | | | | D00425A | A07 | | ALL | |
| 233Z | | | JH | 0-0 | 34-22-19 | D05205P | | 54 | | | | D00425A | | JH | ALL | |
| 234B | 24 | PW | JI | 5-0 | 22-12-31 | D00425B | | B01 | | | | TB0130F | C163 | 2 | 050-099, 280-299 | |
| 234B | 24 | PW | JI | 3-11 | 22-12-31 | D00425B | | B01 | | | | TB0130F | C163 | 2 | 150-199, 275-278 | |
| 234R | 24 | PW | JI | 0-0 | 22-12-31 | D00425B | | A01 | | | | TB0130F | A163 | 2 | ALL | |
| 234Z | | | JI | 0-0 | 22-12-31 | D00425B | | DED | | | | GDY0009 | S.. | 2 | 050-099, 150-199, 275-276 | |
| 234Z | | | JI | 0-0 | 22-12-31 | D00425B | | DED | | | | GDY0010 | S.. | 2 | 277-299 | |
| 235W | 24 | 7K | JJ | 0-6 | 34-43-11 | D00425D | | E01 | | | | TB0205G | 9 | 2 | ALL | |
| 235WB | 24 | 7K | JJ | 0-0 | 34-43-11 | D00425D | | F01 | | | | TB0205G | 8 | 2 | ALL | |
| 235Z | | | JJ | 0-0 | 34-43-11 | D00425D | | DED | | | | GDZ0001 | S.. | 2 | ALL | |
| 236 | 20 | UA | | 1-6 | 22-12-11 | D00425A | | REF | | JK | | GDX0001 | S.. | 2 | ALL | |
| 236B | 24 | PW | JK | 3-0 | 22-12-11 | D00425A | | B01 | | | | D05603J | 2 | | 050-099, 280-299 | |
| 236B | 24 | PW | JK | 2-0 | 22-12-11 | D00425A | | B01 | | | | D05603J | 2 | | 150-199, 275-278 | |
| 236R | 24 | PW | JK | 0-0 | 22-12-11 | D00425A | | A01 | | | | D05603J | 1 | | ALL | |
| 236Z | | | JK | 0-0 | 22-12-11 | D00425A | | REF | | JK | | D05603J | 3 | | ALL | |
| 237B | 24 | PW | JL | 5-0 | 22-12-21 | D00425D | | B01 | | | | TB0130F | C153 | 2 | 050-099, 280-299 | |
| 237B | 24 | PW | JL | 3-8 | 22-12-21 | D00425D | | B01 | | | | TB0130F | C153 | 2 | 150-199, 275-278 | |
| 237R | 24 | PW | JL | 0-0 | 22-12-21 | D00425D | | A01 | | | | TB0130F | A153 | 2 | ALL | |
| 237Z | | | JL | 0-0 | 22-12-21 | D00425D | | DED | | | | GDY0009 | S.. | 2 | ALL | |
| 238W | 24 | 7K | JM | 0-6 | 34-43-11 | D00425A | | E01 | | | | TB0205G | 7 | 2 | ALL | |
| 238WB | 24 | 7K | JM | 0-0 | 34-43-11 | D00425A | | F01 | | | | TB0205G | 6 | 2 | ALL | |
| 238Z | | | JM | 0-0 | 34-43-11 | D00425A | | DED | | | | GDZ0001 | S.. | 2 | ALL | |
| 239 | 20 | UA | | 3-0 | 34-22-18 | D00425A | | | | JN | | GDX0001 | S.. | 2 | 050-099, 280-299 | |
| 239 | 20 | UA | | 1-8 | 34-22-18 | D00425A | | | | JN | | GDX0001 | S.. | 2 | 150-199, 275-278 | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 19

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | |
| 239B | 24 | PW | JN | 3-0 | 34-22-18 | D00425A | H06 | | | D05653J | 7 | | | 050-099, 280-299 | |
| 239B | 24 | PW | JN | 2-3 | 34-22-18 | D00425A | H06 | | | D05653J | 7 | | | 150-199, 275-278 | |
| 239R | 24 | PW | JN | 0-0 | 34-22-18 | D00425A | G06 | | | D05653J | 6 | | | ALL | |
| 239Z | | | JN | 0-0 | 34-22-18 | D00425A | | | JN | D05653J | 8 | | | ALL | |
| 240B | 24 | PW | JO | 3-0 | 34-22-18 | D00425D | H06 | | | TB0130F | C115 | 2 | | 050-099, 280-299 | |
| 240B | 24 | PW | JO | 2-3 | 34-22-18 | D00425D | H06 | | | TB0130F | C115 | 2 | | 150-199, 275-278 | |
| 240R | 24 | PW | JO | 0-0 | 34-22-18 | D00425D | G06 | | | TB0130F | A115 | 2 | | ALL | |
| 240Z | | | JO | 0-0 | 34-22-18 | D00425D | DED | | | GDY0002 | S.. | 2 | | ALL | |
| 241B | 24 | PW | JP | 4-0 | 34-46-11 | D05205P | 42 | | | TB0130H | 113 | 2 | | 050-099, 280-299 | |
| 241B | 24 | PW | JP | 3-6 | 34-46-11 | D05205P | 42 | | | TB0130H | 113 | 2 | | 150-199, 275-278 | |
| 241R | 24 | PW | JP | 0-0 | 34-46-11 | D05205P | 41 | | | TB0130H | 111 | 2 | | ALL | |
| 241Z | | | JP | 0-0 | 34-46-11 | D05205P | 43 | | | GDY0002 | S.. | 2 | | ALL | |
| 242 | 20 | UA | | 1-6 | 34-22-19 | D00425A | | | JQ | GDX0001 | S.. | 2 | | ALL | |
| 242B | 24 | PW | JQ | 3-0 | 34-22-19 | D05603J | 27 | | | D00425A | K01 | | | 050-099, 280-299 | |
| 242B | 24 | PW | JQ | 2-0 | 34-22-19 | D05603J | 27 | | | D00425A | K01 | | | 150-199, 275-278 | |
| 242R | 24 | PW | JQ | 0-0 | 34-22-19 | D05603J | 26 | | | D00425A | J01 | | | ALL | |
| 242Z | | | JQ | 0-0 | 34-22-19 | D05603J | 28 | | | D00425A | | | JQ | ALL | |
| 243B | 24 | PW | JR | 3-0 | 34-22-19 | D00425D | K01 | | | TB0130F | C102 | 2 | | 050-099, 280-299 | |
| 243B | 24 | PW | JR | 2-5 | 34-22-19 | D00425D | K01 | | | TB0130F | C102 | 2 | | 150-199, 275-278 | |
| 243R | 24 | PW | JR | 0-0 | 34-22-19 | D00425D | J01 | | | TB0130F | A102 | 2 | | ALL | |
| 243Z | | | JR | 0-0 | 34-22-19 | D00425D | DED | | | GDY0002 | S.. | 2 | | 050-099 | |
| 243Z | | | JR | 0-0 | 34-22-19 | D00425D | DED | | | GDY0001 | S.. | 2 | | 150-199, 275-299 | |
| 244B | 24 | PW | JS | 5-0 | 77-35-11 | D05653J | 2 | | | TB0130X | C051 | BJ | | 050-099, 280-299 | |
| 244B | 24 | PW | JS | 3-6 | 77-35-11 | D05653J | 2 | | | TB0130X | C051 | BJ | | 150-199, 275-278 | |
| 244R | 24 | PW | JS | 0-0 | 77-35-11 | D05653J | 1 | | | TB0130X | D051 | BJ | | ALL | |
| 244Z | | | JS | 0-0 | 77-35-11 | D05653J | 3 | | | GDY0008 | S.. | 2 | | ALL | |
| 245B | 24 | PW | JT | 4-0 | 34-22-18 | TB0130H | 113 | 2 | | D05205P | 14 | | | 050-099, 280-299 | |
| 245B | 24 | PW | JT | 3-6 | 34-22-18 | TB0130H | 113 | 2 | | D05205P | 14 | | | 150-199, 275-278 | |
| 245R | 24 | PW | JT | 0-0 | 34-22-18 | TB0130H | 111 | 2 | | D05205P | 13 | | | ALL | |
| 245Z | | | JT | 0-0 | 34-22-18 | GDY0002 | S.. | 2 | | D05205P | 15 | | | ALL | |
| 246B | 24 | PW | JU | 5-0 | 34-22-18 | TB0130G | 155 | 2 | | D05603J | 43 | | | 050-099, 280-299 | |
| 246B | 24 | PW | JU | 3-8 | 34-22-18 | TB0130G | 155 | 2 | | D05603J | 43 | | | 150-199, 275-278 | |
| 246R | 24 | PW | JU | 0-0 | 34-22-18 | TB0130G | 154 | 2 | | D05603J | 42 | | | ALL | |
| 246Z | | | JU | 0-0 | 34-22-18 | GDY0008 | S.. | 2 | | D05603J | 44 | | | 050-099 | |
| 246Z | | | JU | 0-0 | 34-22-18 | GDY0009 | S.. | 2 | | D05603J | 44 | | | 150-199, 275-299 | |
| 247B | 24 | PW | JV | 4-0 | 34-22-19 | TB0130G | 13 | 2 | | D05205P | 17 | | | 050-099, 280-299 | |
| 247B | 24 | PW | JV | 3-7 | 34-22-19 | TB0130G | 13 | 2 | | D05205P | 17 | | | 150-199, 275-278 | |
| 247R | 24 | PW | JV | 0-0 | 34-22-19 | TB0130G | 12 | 2 | | D05205P | 16 | | | ALL | |
| 247Z | | | JV | 0-0 | 34-22-19 | GDY0002 | S.. | 2 | | D05205P | 18 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 20

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | | |
| 248B | 24 | PW | JW | 4-0 | 34-22-19 | TB0130G | 22 | 2 | | D05205P | 20 | | | 050-099, 280-299 | | |
| 248B | 24 | PW | JW | 2-10 | 34-22-19 | TB0130G | 22 | 2 | | D05205P | 20 | | | 150-199, 275-278 | | |
| 248R | 24 | PW | JW | 0-0 | 34-22-19 | TB0130G | 21 | 2 | | D05205P | 19 | | | ALL | | |
| 248Z | | | JW | 0-0 | 34-22-19 | GDY0005 | S.. | 2 | | D05205P | 21 | | | ALL | | |
| 249B | 24 | PW | JX | 4-0 | 34-46-11 | TB0130H | 123 | 2 | | D05205P | 29 | | | 050-099, 280-299 | | |
| 249B | 24 | PW | JX | 2-8 | 34-46-11 | TB0130H | 123 | 2 | | D05205P | 29 | | | 150-199, 275-278 | | |
| 249R | 24 | PW | JX | 0-0 | 34-46-11 | TB0130H | 121 | 2 | | D05205P | 28 | | | ALL | | |
| 249Z | | | JX | 0-0 | 34-46-11 | GDY0005 | S.. | 2 | | D05205P | 30 | | | ALL | | |
| 250B | 24 | PW | JY | 5-0 | 34-22-14 | TB0130H | 25 | 2 | | D05097P | 40 | | | 050-099, 280-299 | | |
| 250B | 24 | PW | JY | 3-9 | 34-22-14 | TB0130H | 25 | 2 | | D05097P | 40 | | | 150-199, 275-278 | | |
| 250R | 24 | PW | JY | 0-0 | 34-22-14 | TB0130H | 23 | 2 | | D05097P | 39 | | | ALL | | |
| 250Z | | | JY | 0-0 | 34-22-14 | GDY0005 | S.. | 2 | | D05097P | 41 | | | ALL | | |
| 251W | 24 | 7K | KA | 4-0 | 34-43-11 | TB0205G | 7 | 2 | | D04923P | 18 | | | 050-099, 280-299 | | |
| 251W | 24 | 7K | KA | 3-4 | 34-43-11 | TB0205G | 7 | 2 | | D04923P | 18 | | | 150-199, 275-278 | | |
| 251WB | 24 | 7K | KA | 0-0 | 34-43-11 | TB0205G | 6 | 2 | | D04923P | 19 | | | ALL | | |
| 251Z | | | KA | 0-0 | 34-43-11 | D04923P | 20 | | | GDZ0001 | S.. | 2 | | ALL | | |
| 252W | 24 | 7K | KB | 4-0 | 34-43-11 | TB0205G | 7 | 2 | | D04889P | 5 | | | 050-099, 280-299 | | |
| 252W | 24 | 7K | KB | 2-9 | 34-43-11 | TB0205G | 7 | 2 | | D04889P | 5 | | | 150-199, 275-278 | | |
| 252WB | 24 | 7K | KB | 0-0 | 34-43-11 | TB0205G | 6 | 2 | | D04889P | 6 | | | ALL | | |
| 252Z | | | KB | 0-0 | 34-43-11 | D04889P | 7 | | | GDZ0001 | S.. | 2 | | ALL | | |
| 253B | 24 | PW | KC | 4-0 | 34-43-11 | D05603J | 24 | | | D04889P | 9 | | | 050-099, 280-299 | | |
| 253B | 24 | PW | KC | 2-9 | 34-43-11 | D05603J | 24 | | | D04889P | 9 | | | 150-199, 275-278 | | |
| 253R | 24 | PW | KC | 0-0 | 34-43-11 | D05603J | 23 | | | D04889P | 8 | | | ALL | | |
| 253Z | | | KC | 0-0 | 34-43-11 | D05603J | 25 | | | D04889P | 10 | | | ALL | | |
| 254B | 24 | PW | KD | 6-0 | 34-43-11 | TB0130G | 162 | 2 | | D04889P | 12 | | | 050-099, 280-299 | | |
| 254B | 24 | PW | KD | 4-9 | 34-43-11 | TB0130G | 162 | 2 | | D04889P | 12 | | | 150-199, 275-278 | | |
| 254R | 24 | PW | KD | 0-0 | 34-43-11 | TB0130G | 161 | 2 | | D04889P | 11 | | | ALL | | |
| 254Z | | | KD | 0-0 | 34-43-11 | GDY0009 | S.. | 2 | | D04889P | 13 | | | 050-099, 150-199, 275-276 | | |
| 254Z | | | KD | 0-0 | 34-43-11 | GDY0010 | S.. | 2 | | D04889P | 13 | | | 277-299 | | |
| 255B | 24 | PW | KE | 5-0 | 34-43-11 | TB0130H | 25 | 2 | | D04889P | 3 | | | 050-099, 280-299 | | |
| 255B | 24 | PW | KE | 3-11 | 34-43-11 | TB0130H | 25 | 2 | | D04889P | 3 | | | 150-199, 275-278 | | |
| 255R | 24 | PW | KE | 0-0 | 34-43-11 | TB0130H | 23 | 2 | | D04889P | 2 | | | ALL | | |
| 255Z | | | KE | 0-0 | 34-43-11 | GDY0005 | S.. | 2 | | D04889P | 4 | | | ALL | | |
| 256B | 24 | PW | KF | 4-0 | 34-22-35 | TB0130H | 25 | 2 | | D04923P | 16 | | | 050-099, 280-299 | | |
| 256B | 24 | PW | KF | 3-1 | 34-22-35 | TB0130H | 25 | 2 | | D04923P | 16 | | | 150-199, 275-278 | | |
| 256R | 24 | PW | KF | 0-0 | 34-22-35 | TB0130H | 23 | 2 | | D04923P | 15 | | | ALL | | |
| 256Z | | | KF | 0-0 | 34-22-35 | GDY0005 | S.. | 2 | | D04923P | 17 | | | ALL | | |
| 257B | 24 | PW | KG | 5-0 | 34-22-39 | D04923P | 7 | | | TB0130G | 13 | 2 | | 050-099, 280-299 | | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 21

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | | | |
| 257B | 24 | PW | KG | 3-10 | 34-22-39 | D04923P | | 7 | | | | | TB0130G | 13 | 2 | | 150-199, 275-278 |
| 257R | 24 | PW | KG | 0-0 | 34-22-39 | D04923P | | 6 | | | | | TB0130G | 12 | 2 | | ALL |
| 257Z | | | KG | 0-0 | 34-22-39 | D04923P | | 8 | | | | | GDY0002 | S.. | 2 | | ALL |
| 258B | 24 | PW | KH | 4-0 | 34-22-39 | D04923P | | 10 | | | | | TB0130G | 22 | 2 | | 050-099, 280-299 |
| 258B | 24 | PW | KH | 3-1 | 34-22-39 | D04923P | | 10 | | | | | TB0130G | 22 | 2 | | 150-199, 275-278 |
| 258R | 24 | PW | KH | 0-0 | 34-22-39 | D04923P | | 9 | | | | | TB0130G | 21 | 2 | | ALL |
| 258Z | | | KH | 0-0 | 34-22-39 | D04923P | | 11 | | | | | GDY0005 | S.. | 2 | | ALL |
| 259B | 24 | PW | KI | 5-0 | 34-22-38 | D05223P | | 13 | | | | | TB0130H | 113 | 2 | | 050-099, 275-276, 280-299 |
| 259B | 24 | PW | KI | 3-11 | 34-22-38 | D05223P | | 13 | | | | | TB0130H | 113 | 2 | | 150-199, 277-278 |
| 259R | 24 | PW | KI | 0-0 | 34-22-38 | D05223P | | 12 | | | | | TB0130H | 111 | 2 | | ALL |
| 259Z | | | KI | 0-0 | 34-22-38 | D05223P | | 14 | | | | | GDY0002 | S.. | 2 | | ALL |
| 261B | 24 | PW | KK | 5-0 | 34-22-82 | TB0130G | | 155 | 2 | | | | D05581P | 8 | | | 050-099, 280-299 |
| 261B | 24 | PW | KK | 4-6 | 34-22-82 | TB0130G | | 155 | 2 | | | | D05581P | 8 | | | 150-199, 275-278 |
| 261R | 24 | PW | KK | 0-0 | 34-22-82 | TB0130G | | 154 | 2 | | | | D05581P | 7 | | | ALL |
| 261Z | | | KK | 0-0 | 34-22-82 | GDY0008 | | S.. | 2 | | | | D05581P | 9 | | | 050-099 |
| 261Z | | | KK | 0-0 | 34-22-82 | GDY0009 | | S.. | 2 | | | | D05581P | 9 | | | 150-199, 275-299 |
| 262B | 24 | PW | KL | 5-0 | 34-22-81 | TB0130G | | 22 | 2 | | | | D05581P | 11 | | | 050-099 |
| 262B | 24 | PW | KL | 3-10 | 34-22-81 | TB0130G | | 22 | 2 | | | | D05581P | 11 | | | 150-156, 162-166 |
| 262R | 24 | PW | KL | 0-0 | 34-22-81 | TB0130G | | 21 | 2 | | | | D05581P | 10 | | | 050-099, 150-156, 162-166 |
| 262Z | | | KL | 0-0 | 34-22-81 | GDY0005 | | S.. | 2 | | | | D05581P | 12 | | | 050-099, 150-156, 162-166 |
| 263B | 24 | PW | KM | 4-0 | 34-22-81 | TB0130G | | 13 | 2 | | | | D05581P | 14 | | | 050-099, 280-299 |
| 263B | 24 | PW | KM | 3-3 | 34-22-81 | TB0130G | | 13 | 2 | | | | D05581P | 14 | | | 150-199, 275-278 |
| 263R | 24 | PW | KM | 0-0 | 34-22-81 | TB0130G | | 12 | 2 | | | | D05581P | 13 | | | ALL |
| 263Z | | | KM | 0-0 | 34-22-81 | GDY0002 | | S.. | 2 | | | | D05581P | 15 | | | ALL |
| 264B | 24 | PW | KN | 4-0 | 34-61-14 | TB0130H | | 25 | 2 | | | | D05205P | 23 | | | 050-099, 280-299 |
| 264B | 24 | PW | KN | 2-10 | 34-61-14 | TB0130H | | 25 | 2 | | | | D05205P | 23 | | | 150-199, 275-278 |
| 264R | 24 | PW | KN | 0-0 | 34-61-14 | TB0130H | | 23 | 2 | | | | D05205P | 22 | | | ALL |
| 264Z | | | KN | 0-0 | 34-61-14 | GDY0005 | | S.. | 2 | | | | D05205P | 24 | | | ALL |
| 265B | 24 | PW | KO | 4-0 | 34-33-11 | TB0130H | | 123 | 2 | | | | D05603J | 17 | | | 050-099, 280-299 |
| 265B | 24 | PW | KO | 2-11 | 34-33-11 | TB0130H | | 123 | 2 | | | | D05603J | 17 | | | 150-199, 275-278 |
| 265R | 24 | PW | KO | 0-0 | 34-33-11 | TB0130H | | 121 | 2 | | | | D05603J | 16 | | | ALL |
| 265Z | | | KO | 0-0 | 34-33-11 | GDY0005 | | S.. | 2 | | | | D05603J | 18 | | | ALL |
| 267B | 24 | PW | KQ | 5-0 | 77-35-11 | D05653J | | 11 | | | | | TB0130X | A051 | BJ | | 050-099, 280-299 |
| 267B | 24 | PW | KQ | 3-6 | 77-35-11 | D05653J | | 11 | | | | | TB0130X | A051 | BJ | | 150-199, 275-278 |
| 267R | 24 | PW | KQ | 0-0 | 77-35-11 | D05653J | | 10 | | | | | TB0130X | B051 | BJ | | ALL |
| 267Z | | | KQ | 0-0 | 77-35-11 | D05653J | | 12 | | | | | GDY0008 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 22

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | | | |
| 268B | 24 | PW | KR | | 4-0 | 34-22-13 | D04923P | | 31 | | | | TB0130G | 131 | 2 | | 050-099, 280-299 |
| 268B | 24 | PW | KR | | 3-1 | 34-22-13 | D04923P | | 31 | | | | TB0130G | 131 | 2 | | 150-199, 275-278 |
| 268R | 24 | PW | KR | | 0-0 | 34-22-13 | D04923P | | 30 | | | | TB0130G | 130 | 2 | | ALL |
| 268Z | | | KR | | 0-0 | 34-22-13 | D04923P | | 32 | | | | GDY0007 | S.. | 2 | | ALL |
| 269 | 20 | UA | | | 1-6 | 34-22-13 | GDX0001 | | S.. | 2 | | | D00425D | | | KR | 050-099 |
| 269 | 20 | UA | | | 1-8 | 34-22-13 | GDX0001 | | S.. | 2 | | | D00425D | | | KR | 150-199, 275-278 |
| 269 | 20 | UA | | | 3-0 | 34-22-13 | GDX0001 | | S.. | 2 | | | D00425D | | | KR | 280-299 |
| 269B | 24 | PW | KS | | 5-0 | 34-22-13 | D04923P | | 34 | | | | D00425D | D02 | | | 050-099, 280-299 |
| 269B | 24 | PW | KS | | 3-2 | 34-22-13 | D04923P | | 34 | | | | D00425D | D02 | | | 150-199, 275-278 |
| 269R | 24 | PW | KS | | 0-0 | 34-22-13 | D04923P | | 33 | | | | D00425D | C02 | | | ALL |
| 269Z | | | KS | | 0-0 | 34-22-13 | D04923P | | 35 | | | | D00425D | | | KR | ALL |
| 270 | 20 | UA | | | 1-6 | 34-22-13 | GDX0001 | | S.. | 2 | | | D00425A | | | KT | 050-099 |
| 270 | 20 | UA | | | 1-8 | 34-22-13 | GDX0001 | | S.. | 2 | | | D00425A | | | KT | 150-199, 275-278 |
| 270 | 20 | UA | | | 3-0 | 34-22-13 | GDX0001 | | S.. | 2 | | | D00425A | | | KT | 280-299 |
| 270B | 24 | PW | KT | | 5-0 | 34-22-13 | D04923P | | 45 | | | | D00425A | D02 | | | 050-099, 280-299 |
| 270B | 24 | PW | KT | | 3-2 | 34-22-13 | D04923P | | 45 | | | | D00425A | D02 | | | 150-199, 275-278 |
| 270R | 24 | PW | KT | | 0-0 | 34-22-13 | D04923P | | 44 | | | | D00425A | C02 | | | ALL |
| 270Z | | | KT | | 0-0 | 34-22-13 | D04923P | | 46 | | | | D00425A | | | KT | ALL |
| 271B | 24 | PW | KU | | 4-0 | 31-31-12 | D00425E | | B13 | | | | TB0130G | 131 | 2 | | 050-099, 280-299 |
| 271B | 24 | PW | KU | | 3-1 | 31-31-12 | D00425E | | B13 | | | | TB0130G | 131 | 2 | | 150-199, 275-278 |
| 271R | 24 | PW | KU | | 0-0 | 31-31-12 | D00425E | | A13 | | | | TB0130G | 130 | 2 | | ALL |
| 271Z | | | KU | | 0-0 | 31-31-12 | D00425E | | DED | | | | GDY0007 | S.. | 2 | | ALL |
| 272B | 22 | PR | KV | | 4-0 | 31-31-22 | TB0130X | | A133 | BJ | | | D05223P | 8 | | | 050-099, 275-276, 280-299 |
| 272B | 24 | PW | KV | | 3-4 | 31-31-22 | TB0130X | | A133 | BJ | | | D05223P | 8 | | | 150-199 |
| 272B | 22 | PR | KV | | 3-4 | 31-31-22 | TB0130X | | A133 | BJ | | | D05223P | 8 | | | 277-278 |
| 272R | 22 | PR | KV | | 0-0 | 31-31-22 | TB0130X | | A132 | BJ | | | D05223P | 7 | | | 050-099, 275-299 |
| 272R | 24 | PW | KV | | 0-0 | 31-31-22 | TB0130X | | A132 | BJ | | | D05223P | 7 | | | 150-199 |
| 272Z | | | KV | | 0-0 | 31-31-22 | GDY0007 | | S.. | 2 | | | D05223P | 9 | | | ALL |
| 273B | 24 | PW | KW | | 4-0 | 31-31-20 | D04923P | | 54 | | | | TB0130H | 123 | 2 | | 050-099, 280-299 |
| 273B | 24 | PW | KW | | 2-11 | 31-31-20 | D04923P | | 54 | | | | TB0130H | 123 | 2 | | 150-199, 275-278 |
| 273R | 24 | PW | KW | | 0-0 | 31-31-20 | D04923P | | 55 | | | | TB0130H | 121 | 2 | | ALL |
| 273Z | | | KW | | 0-0 | 31-31-20 | D04923P | | 47 | | | | GDY0005 | S.. | 2 | | ALL |
| 274B | 24 | PW | KX | | 4-0 | 34-61-24 | D04923P | | 38 | | | | TB0130H | 25 | 2 | | 050-099, 280-299 |
| 274B | 24 | PW | KX | | 3-1 | 34-61-24 | D04923P | | 38 | | | | TB0130H | 25 | 2 | | 150-199, 275-278 |
| 274R | 24 | PW | KX | | 0-0 | 34-61-24 | D04923P | | 37 | | | | TB0130H | 23 | 2 | | ALL |
| 274Z | | | KX | | 0-0 | 34-61-24 | D04923P | | 40 | | | | GDY0005 | S.. | 2 | | ALL |
| 275B | 24 | PW | KY | | 5-0 | 34-22-38 | D05223P | | 16 | | | | TB0130Y | C159 | BJ | | 050-099, 275-276, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 23

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | |
| 275B | 24 | PW | KY | 3-11 | 34-22-38 | D05223P | | 16 | | | TB0130Y | C159 | BJ | | 150-199, 277-278 |
| 275R | 24 | PW | KY | 0-0 | 34-22-38 | D05223P | | 15 | | | TB0130Y | A159 | BJ | | ALL |
| 275Z | | | KY | 0-0 | 34-22-38 | D05223P | | 17 | | | GDY0009 | S.. | 2 | | ALL |
| 277B | 24 | PW | LB | 5-0 | 34-61-16 | D05205P | | 26 | | | TB0130Y | C159 | BJ | | 050-099, 280-299 |
| 277B | 24 | PW | LB | 3-7 | 34-61-16 | D05205P | | 26 | | | TB0130Y | C159 | BJ | | 150-199, 275-278 |
| 277R | 24 | PW | LB | 0-0 | 34-61-16 | D05205P | | 25 | | | TB0130Y | A159 | BJ | | ALL |
| 277Z | | | LB | 0-0 | 34-61-16 | D05205P | | 27 | | | GDY0009 | S.. | 2 | | ALL |
| 280 | 20 | UA | | 1-6 | 22-41-11 | D00745A | | REF | | LE | GDY0009 | S.. | 2 | | ALL |
| 280B | 24 | PW | LE | 5-0 | 22-41-11 | D00745A | | B15 | | | D05603J | 6 | | | 050-099, 280-299 |
| 280B | 24 | PW | LE | 3-10 | 22-41-11 | D00745A | | B15 | | | D05603J | 6 | | | 150-199, 275-278 |
| 280R | 24 | PW | LE | 0-0 | 22-41-11 | D00745A | | A15 | | | D05603J | 5 | | | ALL |
| 280Z | | | LE | 0-0 | 22-41-11 | D00745A | | REF | | LE | D05603J | 7 | | | ALL |
| 281 | 20 | UA | | 1-6 | 22-41-12 | D00745A | | REF | | LF | GDY0009 | S.. | 2 | | ALL |
| 281B | 24 | PW | LF | 5-0 | 22-41-12 | D00745A | | B11 | | | D05603J | 14 | | | 050-099, 280-299 |
| 281B | 24 | PW | LF | 3-10 | 22-41-12 | D00745A | | B11 | | | D05603J | 14 | | | 150-199, 275-278 |
| 281R | 24 | PW | LF | 0-0 | 22-41-12 | D00745A | | A11 | | | D05603J | 13 | | | ALL |
| 281Z | | | LF | 0-0 | 22-41-12 | D00745A | | REF | | LF | D05603J | 15 | | | ALL |
| 282 | 20 | UA | | 1-6 | 22-32-12 | D00745A | | REF | | LG | GDY0009 | S.. | 2 | | ALL |
| 282B | 24 | PW | LG | 5-0 | 22-32-12 | D00745A | | B03 | | | D05603J | 10 | | | 050-099, 280-299 |
| 282B | 24 | PW | LG | 3-10 | 22-32-12 | D00745A | | B03 | | | D05603J | 10 | | | 150-199, 275-278 |
| 282R | 24 | PW | LG | 0-0 | 22-32-12 | D00745A | | A03 | | | D05603J | 9 | | | ALL |
| 282Z | | | LG | 0-0 | 22-32-12 | D00745A | | REF | | LG | D05603J | 11 | | | ALL |
| 283B | 24 | PW | LH | 4-0 | 22-41-11 | D00745A | | K04 | | | TB0130F | C150 | 2 | | 050-099, 280-299 |
| 283B | 24 | PW | LH | 2-11 | 22-41-11 | D00745A | | K04 | | | TB0130F | C150 | 2 | | 150-199, 275-278 |
| 283R | 24 | PW | LH | 0-0 | 22-41-11 | D00745A | | J04 | | | TB0130F | A150 | 2 | | ALL |
| 283Z | | | LH | 0-0 | 22-41-11 | D00745A | | DED | | | GDY0008 | S.. | 2 | | ALL |
| 284 | 20 | UA | | 1-6 | 22-41-11 | D00745A | | REF | | LI | GDY0009 | S.. | 2 | | ALL |
| 284B | 24 | PW | LI | 4-0 | 22-41-11 | D00745A | | B04 | | | D05205P | 11 | | | 050-099, 280-299 |
| 284B | 24 | PW | LI | 3-7 | 22-41-11 | D00745A | | B04 | | | D05205P | 11 | | | 150-199, 275-278 |
| 284R | 24 | PW | LI | 0-0 | 22-41-11 | D00745A | | A04 | | | D05205P | 10 | | | ALL |
| 284Z | | | LI | 0-0 | 22-41-11 | D00745A | | REF | | LI | D05205P | 12 | | | ALL |
| 285B | 24 | PW | LJ | 4-0 | 22-41-11 | D00745A | | K01 | | | TB0130F | C151 | 2 | | 050-099, 280-299 |
| 285B | 24 | PW | LJ | 2-11 | 22-41-11 | D00745A | | K01 | | | TB0130F | C151 | 2 | | 150-199, 275-278 |
| 285R | 24 | PW | LJ | 0-0 | 22-41-11 | D00745A | | J01 | | | TB0130F | A151 | 2 | | ALL |
| 285Z | | | LJ | 0-0 | 22-41-11 | D00745A | | DED | | | GDY0008 | S.. | 2 | | ALL |
| 286 | 20 | UA | | 1-6 | 22-41-12 | D00745A | | REF | | LK | GDY0009 | S.. | 2 | | ALL |
| 286B | 24 | PW | LK | 5-0 | 22-41-12 | D00745A | | B09 | | | D05205P | 39 | | | 050-099, 280-299 |
| 286B | 24 | PW | LK | 3-7 | 22-41-12 | D00745A | | B09 | | | D05205P | 39 | | | 150-199, 275-278 |
| 286R | 24 | PW | LK | 0-0 | 22-41-12 | D00745A | | A09 | | | D05205P | 38 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 24

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|---|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | | |
| 286Z | | | LK | 0-0 | 22-41-12 | D00745A | REF | | LK | D05205P | 40 | | | ALL | | |
| 287 | 20 | UA | | 1-6 | 22-41-12 | D00745A | REF | | LL | GDX0009 | S.. | 2 | | ALL | | |
| 287B | 24 | PW | LL | 5-0 | 22-41-12 | D00745A | B10 | | | D04923P | 52 | | | 050-099, 280-299 | | |
| 287B | 24 | PW | LL | 3-10 | 22-41-12 | D00745A | B10 | | | D04923P | 52 | | | 150-199, 275-278 | | |
| 287R | 24 | PW | LL | 0-0 | 22-41-12 | D00745A | A10 | | | D04923P | 51 | | | ALL | | |
| 287Z | | | LL | 0-0 | 22-41-12 | D04923P | 53 | | | D00745A | REF | | LL | ALL | | |
| 288B | 24 | PW | LM | 4-0 | 22-41-11 | D00745A | B01 | | | TB0130F | C158 | 2 | | 050-099, 280-299 | | |
| 288B | 24 | PW | LM | 2-9 | 22-41-11 | D00745A | B01 | | | TB0130F | C158 | 2 | | 150-199, 275-278 | | |
| 288R | 24 | PW | LM | 0-0 | 22-41-11 | D00745A | A01 | | | TB0130F | A158 | 2 | | ALL | | |
| 288Z | | | LM | 0-0 | 22-41-11 | D00745A | DED | | | GDX0009 | S.. | 2 | | ALL | | |
| 289B | 24 | PW | LN | 4-0 | 31-31-12 | TB0130G | 131 | 2 | | D05603J | 39 | | | 050-099, 280-299 | | |
| 289B | 24 | PW | LN | 3-1 | 31-31-12 | TB0130G | 131 | 2 | | D05603J | 39 | | | 150-199, 275-278 | | |
| 289R | 24 | PW | LN | 0-0 | 31-31-12 | TB0130G | 130 | 2 | | D05603J | 38 | | | ALL | | |
| 289Z | | | LN | 0-0 | 31-31-12 | GDX0007 | S.. | 2 | | D05603J | 40 | | | ALL | | |
| 290B | 24 | PW | LO | 5-0 | 21-31-11 | D05603J | 51 | | | TB0130F | A066 | 2 | | 050-099, 280-299 | | |
| 290B | 24 | PW | LO | 4-1 | 21-31-11 | D05603J | 51 | | | TB0130F | A066 | 2 | | 150-199, 275-278 | | |
| 290R | 24 | PW | LO | 0-0 | 21-31-11 | D05603J | 50 | | | TB0130F | C066 | 2 | | ALL | | |
| 290Z | | | LO | 0-0 | 21-31-11 | D05603J | 52 | | | TB0130F | A065 | 2 | | ALL | | |
| 294B | 24 | PW | LS | 4-0 | 31-41-31 | D05603J | 21 | | | TB0130H | 123 | 2 | | 050-099, 280-299 | | |
| 294B | 24 | PW | LS | 2-11 | 31-41-31 | D05603J | 21 | | | TB0130H | 123 | 2 | | 150-199, 275-278 | | |
| 294R | 24 | PW | LS | 0-0 | 31-41-31 | D05603J | 20 | | | TB0130H | 121 | 2 | | ALL | | |
| 294Z | | | LS | 0-0 | 31-41-31 | D05603J | 22 | | | GDX0005 | S.. | 2 | | ALL | | |
| 297 | 20 | UA | | 1-6 | 34-46-12 | TB0130H | REF | | LV | GDX0005 | S.. | 2 | | 280-299 | | |
| 297B | 24 | PW | LV | 4-0 | 34-46-12 | D05205P | 32 | | | TB0130H | 25 | 2 | | 280-299 | | |
| 297R | 24 | PW | LV | 0-0 | 34-46-12 | D05205P | 31 | | | TB0130H | 23 | 2 | | 280-299 | | |
| 297Z | | | LV | 0-0 | 34-46-12 | D05205P | 33 | | | TB0130H | REF | | LV | 280-299 | | |
| 298 | 20 | UA | | 1-6 | 34-45-14 | GDX0001 | S.. | 2 | | TB0130Y | REF | | LW | 050-099, 150-152, 155-199, 275-276 | | |
| 298 | 20 | UA | | 1-6 | 34-45-14 | GDX0002 | S.. | 2 | | TB0130Y | REF | | LW | 277-299 | | |
| 298B | 24 | PW | LW | 3-0 | 34-45-14 | D00425A | K09 | | | TB0130Y | C017 | BJ | | 050-099, 280-299 | | |
| 298B | 24 | PW | LW | 2-5 | 34-45-14 | D00425A | K09 | | | TB0130Y | C017 | BJ | | 150-199, 275-278 | | |
| 298R | 24 | PW | LW | 0-0 | 34-45-14 | D00425A | J09 | | | TB0130Y | A017 | BJ | | ALL | | |
| 298Z | | | LW | 0-0 | 34-45-14 | D00425A | DED | | | TB0130Y | REF | | LW | 050-099, 150-152, 155-199, 275-299 | | |
| 298Z | | | LW | 0-0 | 34-45-14 | D00425A | DED | | | TB0130Y | | | FB | 153-154 | | |
| 500 | 20 | UA | | 1-6 | 34-45-14 | GDX0001 | S.. | 2 | | TB0130Y | REF | | TY | 050-099, 150-152, 155-156, 162-166, 275-276 | | |
| 500B | 24 | PW | TY | 4-0 | 34-45-14 | D04889P | 15 | | | TB0130Y | C017 | BJ | | 050-099 | | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 25

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | |
| 500B | 24 | PW | TY | | 3-3 | 34-45-14 | D04889P | | 15 | | TB0130Y | C017 | BJ | | 150-156, 162-166, 275-276 |
| 500R | 24 | PW | TY | | 0-0 | 34-45-14 | D04889P | | 14 | | TB0130Y | A017 | BJ | | 050-099, 150-156, 162-166, 275-276 |
| 500Z | | | TY | | 0-0 | 34-45-14 | D04889P | | 16 | | TB0130Y | REF | | TY | 050-099, 150-152, 155-156, 162-166, 275-276 |
| 500Z | | | TY | | 0-0 | 34-45-14 | D04889P | | 16 | | TB0130Y | | | FB | 153-154 |
| 501W | 26 | BW | UA | | 4-0 | 34-22-35 | D00425B | B07 | | | D04371P | | 2 | | 050-099, 280-299 |
| 501W | 26 | BW | UA | | 2-6 | 34-22-35 | D00425B | B07 | | | D04371P | | 2 | | 150-199, 275-278 |
| 501WN | 26 | BW | UA | | 0-0 | 34-22-35 | D00425B | A07 | | | D04371P | | 1 | | ALL |
| 501Z | | | UA | | 0-0 | 34-22-35 | GDZ0003 | S.. | 2 | | D04371P | | 3 | | ALL |
| 502W | 26 | BW | UB | | 4-0 | 34-22-35 | D00425B | B08 | | | D04371P | | 5 | | 050-099, 280-299 |
| 502W | 26 | BW | UB | | 2-6 | 34-22-35 | D00425B | B08 | | | D04371P | | 5 | | 150-199, 275-278 |
| 502WN | 26 | BW | UB | | 0-0 | 34-22-35 | D00425B | A08 | | | D04371P | | 4 | | ALL |
| 502Z | | | UB | | 0-0 | 34-22-35 | GDZ0003 | S.. | 2 | | D04371P | | 6 | | ALL |
| 503W | 26 | BW | UC | | 4-0 | 34-22-35 | D00425B | B09 | | | D04371P | | 8 | | 050-099, 280-299 |
| 503W | 26 | BW | UC | | 2-6 | 34-22-35 | D00425B | B09 | | | D04371P | | 8 | | 150-199, 275-278 |
| 503WN | 26 | BW | UC | | 0-0 | 34-22-35 | D00425B | A09 | | | D04371P | | 7 | | ALL |
| 503Z | | | UC | | 0-0 | 34-22-35 | GDZ0003 | S.. | 2 | | D04371P | | 9 | | ALL |
| 504W | 26 | BW | UD | | 4-0 | 34-22-35 | D00425B | B10 | | | D04371P | | 11 | | 050-099, 280-299 |
| 504W | 26 | BW | UD | | 2-6 | 34-22-35 | D00425B | B10 | | | D04371P | | 11 | | 150-199, 275-278 |
| 504WN | 26 | BW | UD | | 0-0 | 34-22-35 | D00425B | A10 | | | D04371P | | 10 | | ALL |
| 504Z | | | UD | | 0-0 | 34-22-35 | GDZ0003 | S.. | 2 | | D04371P | | 12 | | ALL |
| 505W | 26 | BW | UE | | 4-0 | 34-22-35 | D00425B | B11 | | | D04371P | | 14 | | 050-099, 280-299 |
| 505W | 26 | BW | UE | | 2-6 | 34-22-35 | D00425B | B11 | | | D04371P | | 14 | | 150-199, 275-278 |
| 505WN | 26 | BW | UE | | 0-0 | 34-22-35 | D00425B | A11 | | | D04371P | | 13 | | ALL |
| 505Z | | | UE | | 0-0 | 34-22-35 | GDZ0003 | S.. | 2 | | D04371P | | 15 | | ALL |
| 506W | 26 | BW | UF | | 4-0 | 34-22-35 | D00425B | B12 | | | D04371P | | 17 | | 050-099, 280-299 |
| 506W | 26 | BW | UF | | 2-6 | 34-22-35 | D00425B | B12 | | | D04371P | | 17 | | 150-199, 275-278 |
| 506WN | 26 | BW | UF | | 0-0 | 34-22-35 | D00425B | A12 | | | D04371P | | 16 | | ALL |
| 506Z | | | UF | | 0-0 | 34-22-35 | GDZ0003 | S.. | 2 | | D04371P | | 18 | | ALL |
| 507W | 26 | BW | UG | | 4-0 | 34-22-35 | D00425B | B13 | | | D04371P | | 20 | | 050-099, 280-299 |
| 507W | 26 | BW | UG | | 2-6 | 34-22-35 | D00425B | B13 | | | D04371P | | 20 | | 150-199, 275-278 |
| 507WN | 26 | BW | UG | | 0-0 | 34-22-35 | D00425B | A13 | | | D04371P | | 19 | | ALL |
| 507Z | | | UG | | 0-0 | 34-22-35 | GDZ0003 | S.. | 2 | | D04371P | | 21 | | ALL |
| 508W | 26 | BW | UH | | 4-0 | 34-22-35 | D00425B | B14 | | | D04371P | | 23 | | 050-099, 280-299 |
| 508W | 26 | BW | UH | | 2-6 | 34-22-35 | D00425B | B14 | | | D04371P | | 23 | | 150-199, 275-278 |
| 508WN | 26 | BW | UH | | 0-0 | 34-22-35 | D00425B | A14 | | | D04371P | | 22 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 26

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | | |
| 508Z | | | | UH | 0-0 | 34-22-35 | GDZ0003 | S.. | 2 | | D04371P | 24 | | | ALL | |
| 509W | 26 | BW | UI | | 4-0 | 34-22-35 | D00425B | B15 | | | D04371P | 26 | | | 050-099, 280-299 | |
| 509W | 26 | BW | UI | | 2-6 | 34-22-35 | D00425B | B15 | | | D04371P | 26 | | | 150-199, 275-278 | |
| 509WN | 26 | BW | UI | | 0-0 | 34-22-35 | D00425B | A15 | | | D04371P | 25 | | | ALL | |
| 509Z | | | | UI | 0-0 | 34-22-35 | GDZ0003 | S.. | 2 | | D04371P | 27 | | | ALL | |
| 510W | 26 | BW | UJ | | 4-0 | 34-22-35 | D00425B | K07 | | | D04371P | 29 | | | 050-099, 280-299 | |
| 510W | 26 | BW | UJ | | 2-6 | 34-22-35 | D00425B | K07 | | | D04371P | 29 | | | 150-199, 275-278 | |
| 510WN | 26 | BW | UJ | | 0-0 | 34-22-35 | D00425B | J07 | | | D04371P | 28 | | | ALL | |
| 510Z | | | | UJ | 0-0 | 34-22-35 | GDZ0001 | S.. | 2 | | D04371P | 30 | | | ALL | |
| 511W | 26 | BW | UK | | 4-0 | 34-22-35 | D00425B | K08 | | | D04371P | 32 | | | 050-099, 280-299 | |
| 511W | 26 | BW | UK | | 2-6 | 34-22-35 | D00425B | K08 | | | D04371P | 32 | | | 150-199, 275-278 | |
| 511WN | 26 | BW | UK | | 0-0 | 34-22-35 | D00425B | J08 | | | D04371P | 31 | | | ALL | |
| 511Z | | | | UK | 0-0 | 34-22-35 | GDZ0001 | S.. | 2 | | D04371P | 33 | | | ALL | |
| 512W | 26 | BW | UL | | 4-0 | 34-22-35 | D00425B | K09 | | | D04371P | 35 | | | 050-099, 280-299 | |
| 512W | 26 | BW | UL | | 2-6 | 34-22-35 | D00425B | K09 | | | D04371P | 35 | | | 150-199, 275-278 | |
| 512WN | 26 | BW | UL | | 0-0 | 34-22-35 | D00425B | J09 | | | D04371P | 34 | | | ALL | |
| 512Z | | | | UL | 0-0 | 34-22-35 | GDZ0001 | S.. | 2 | | D04371P | 36 | | | ALL | |
| 513W | 26 | BW | UM | | 4-0 | 34-22-35 | D00425B | K10 | | | D04371P | 38 | | | 050-099, 280-299 | |
| 513W | 26 | BW | UM | | 2-6 | 34-22-35 | D00425B | K10 | | | D04371P | 38 | | | 150-199, 275-278 | |
| 513WN | 26 | BW | UM | | 0-0 | 34-22-35 | D00425B | J10 | | | D04371P | 37 | | | ALL | |
| 513Z | | | | UM | 0-0 | 34-22-35 | GDZ0001 | S.. | 2 | | D04371P | 39 | | | ALL | |
| 514W | 26 | BW | UN | | 4-0 | 34-22-35 | D00425B | K11 | | | D04371P | 41 | | | 050-099, 280-299 | |
| 514W | 26 | BW | UN | | 2-6 | 34-22-35 | D00425B | K11 | | | D04371P | 41 | | | 150-199, 275-278 | |
| 514WN | 26 | BW | UN | | 0-0 | 34-22-35 | D00425B | J11 | | | D04371P | 40 | | | ALL | |
| 514Z | | | | UN | 0-0 | 34-22-35 | GDZ0001 | S.. | 2 | | D04371P | 42 | | | ALL | |
| 515W | 26 | BW | UO | | 4-0 | 34-22-35 | D00425B | K12 | | | D04371P | 44 | | | 050-099, 280-299 | |
| 515W | 26 | BW | UO | | 2-6 | 34-22-35 | D00425B | K12 | | | D04371P | 44 | | | 150-199, 275-278 | |
| 515WN | 26 | BW | UO | | 0-0 | 34-22-35 | D00425B | J12 | | | D04371P | 43 | | | ALL | |
| 515Z | | | | UO | 0-0 | 34-22-35 | GDZ0001 | S.. | 2 | | D04371P | 45 | | | ALL | |
| 516W | 26 | BW | UP | | 4-0 | 34-22-35 | D00425B | K13 | | | D04371P | 47 | | | 050-099, 280-299 | |
| 516W | 26 | BW | UP | | 2-6 | 34-22-35 | D00425B | K13 | | | D04371P | 47 | | | 150-199, 275-278 | |
| 516WN | 26 | BW | UP | | 0-0 | 34-22-35 | D00425B | J13 | | | D04371P | 46 | | | ALL | |
| 516Z | | | | UP | 0-0 | 34-22-35 | GDZ0001 | S.. | 2 | | D04371P | 48 | | | ALL | |
| 517W | 26 | BW | UQ | | 4-0 | 34-22-35 | D00425B | K14 | | | D04371P | 50 | | | 050-099, 280-299 | |
| 517W | 26 | BW | UQ | | 2-6 | 34-22-35 | D00425B | K14 | | | D04371P | 50 | | | 150-199, 275-278 | |
| 517WN | 26 | BW | UQ | | 0-0 | 34-22-35 | D00425B | J14 | | | D04371P | 49 | | | ALL | |
| 517Z | | | | UQ | 0-0 | 34-22-35 | GDZ0001 | S.. | 2 | | D04371P | 51 | | | ALL | |
| 518W | 26 | BW | UR | | 4-0 | 34-22-35 | D00425B | K15 | | | D04371P | 53 | | | 050-099, 280-299 | |
| 518W | 26 | BW | UR | | 2-6 | 34-22-35 | D00425B | K15 | | | D04371P | 53 | | | 150-199, 275-278 | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 27

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | |
| 518WN | 26 | BW | UR | 0-0 | 34-22-35 | D00425B | J15 | | | D04371P | 52 | | | ALL | |
| 518Z | | | UR | 0-0 | 34-22-35 | GDZ0001 | S.. | 2 | | D04371P | 54 | | | ALL | |
| 519B | 24 | PW | US | 5-0 | 22-41-13 | D00745A | K15 | | | TB0130G | 110 | 2 | | 050-099, 280-299 | |
| 519B | 24 | PW | US | 4-6 | 22-41-13 | D00745A | K15 | | | TB0130G | 110 | 2 | | 150-199, 275-278 | |
| 519R | 24 | PW | US | 0-0 | 22-41-13 | D00745A | J15 | | | TB0130G | 109 | 2 | | ALL | |
| 519Z | | | US | 0-0 | 22-41-13 | D00745A | DED | | | GDY0002 | S.. | 2 | | 050-099, 150-154, 275-276 | |
| 519Z | | | US | 0-0 | 22-41-13 | D00745A | DED | | | GDY0001 | S.. | 2 | | 155-199, 277-299 | |
| 522 | 20 | UA | | 1-6 | 34-45-14 | GDX0001 | S.. | 2 | | TB0130Y | REF | | UV | 050-099, 150-152, 155-199, 275-276 | |
| 522 | 20 | UA | | 1-6 | 34-45-14 | GDY0002 | S.. | 2 | | TB0130Y | REF | | UV | 277-299 | |
| 522B | 24 | PW | UV | 4-0 | 34-45-14 | D05653J | 24 | | | TB0130Y | C017 | BJ | | 050-099, 280-299 | |
| 522B | 24 | PW | UV | 2-8 | 34-45-14 | D05653J | 24 | | | TB0130Y | C017 | BJ | | 150-199, 275-278 | |
| 522R | 24 | PW | UV | 0-0 | 34-45-14 | D05653J | 23 | | | TB0130Y | A017 | BJ | | ALL | |
| 522Z | | | UV | 0-0 | 34-45-14 | D05653J | 25 | | | TB0130Y | REF | | UV | 050-099, 150-152, 155-199, 275-299 | |
| 522Z | | | UV | 0-0 | 34-45-14 | D05653J | 25 | | | GDY0002 | S.. | 2 | | 153-154 | |
| 601 | 22 | PA | | 3-0 | 34-22-16 | D00425D | G12 | | | D05603J | 41 | | | 050-099, 280-299 | |
| 601 | 22 | PA | | 2-0 | 34-22-16 | D00425D | G12 | | | D05603J | 41 | | | 150-199, 275-278 | |
| 602 | 22 | PA | | 2-3 | 34-45-14 | D00425E | E11 | | | D05653J | 9 | | | 157, 167-199, 277-278 | |
| 602 | 22 | PA | | 4-0 | 34-45-14 | D00425E | E11 | | | D05653J | 9 | | | 280-299 | |
| 603 | 22 | PA | | 5-0 | 34-45-13 | D05653J | 4 | | | TB0130G | 137 | 2 | | 050-099, 280-299 | |
| 603 | 22 | PA | | 3-0 | 34-45-13 | D05653J | 4 | | | TB0130G | 137 | 2 | | 150-152, 155-199, 275-278 | |
| 603 | 22 | PA | | 3-11 | 34-45-13 | D05653J | 4 | | | TB0130F | C069 | 2 | | 153-154 | |
| 604 | 22 | PA | | 3-0 | 34-22-16 | D00425B | G03 | | | GDX0003 | REF | # | | 050-099 | |
| 604 | 22 | PA | | 1-11 | 34-22-16 | D00425B | G03 | | | GDX0003 | REF | # | | 150-152, 155-156, 162-166 | |
| 604 | 22 | PA | | 2-4 | 34-22-16 | D00425B | G03 | | | GDX0005 | REF | # | | 157, 167-199 | |
| 604 | 22 | PA | | 1-11 | 34-22-16 | D00425B | G03 | | | GDX0003 | S.. | # | | 275-276 | |
| 604 | 22 | PA | | 3-0 | 34-22-16 | D00425B | G03 | | | GDX0005 | REF | # | | 277-299 | |
| 605 | 22 | PA | | 3-0 | 34-22-16 | D00425B | G12 | | | GDX0003 | REF | # | | 050-099 | |
| 605 | 22 | PA | | 1-11 | 34-22-16 | D00425B | G12 | | | GDX0003 | REF | # | | 150-152, 155-156, 162-166 | |
| 605 | 22 | PA | | 2-4 | 34-22-16 | D00425B | G12 | | | GDX0005 | REF | # | | 157, 167-199 | |
| 605 | 22 | PA | | 1-11 | 34-22-16 | D00425B | G12 | | | GDX0003 | S.. | # | | 275-276 | |
| 605 | 22 | PA | | 3-0 | 34-22-16 | D00425B | G12 | | | GDX0005 | REF | # | | 277-299 | |
| 606 | 22 | PA | | 2-4 | 34-22-16 | D00425B | H03 | | | GDX0005 | S.. | # | | 153-154 | |
| 606 | 22 | PA | | 2-4 | 34-22-16 | D00425B | H03 | | | GDX0005 | REF | # | | 157, 167-199 | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 28

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1103 | 286T1103 | | | E1-2 SHELF EF1S SG,L (continued) | | | | | | | | | | | |
| 606 | 22 | | PA | | 3-0 | 34-22-16 | D00425B | H03 | | | GDX0005 | REF | # | | 277-299 |
| 607 | 22 | | PA | | 2-4 | 34-22-16 | D00425B | J04 | | | GDX0005 | S.. | # | | 153-154 |
| 607 | 22 | | PA | | 2-4 | 34-22-16 | D00425B | J04 | | | GDX0005 | REF | # | | 157, 167-199 |
| 607 | 22 | | PA | | 3-0 | 34-22-16 | D00425B | J04 | | | GDX0005 | REF | # | | 277-299 |
| 608 | 22 | | PA | | 2-4 | 34-22-16 | D00425A | B10 | | | GDX0005 | S.. | # | | 153-154 |
| 608 | 22 | | PA | | 2-4 | 34-22-16 | D00425A | B10 | | | GDX0005 | REF | # | | 157, 167-199 |
| 608 | 22 | | PA | | 3-0 | 34-22-16 | D00425A | B10 | | | GDX0005 | REF | # | | 277-299 |
| 609 | 22 | | PA | | 2-4 | 34-22-16 | D00425B | B02 | | | GDX0005 | S.. | # | | 153-154 |
| 901W | 24 | | PW | B | 1-0 | 34-43-11 | D04889P | 20 | | | D04889P | 17 | | | 150, 152-199, 275-299 |
| 901WB | 24 | | PW | B | 0-0 | 34-43-11 | D04889P | 21 | | | D04889P | 18 | | | 150, 152-199, 275-299 |
| 901Z | | | | B | 0-0 | 34-43-11 | D04889P | 22 | | | D04889P | 19 | | | 150, 152-199, 275-299 |
| FRB | | | | | 0-0 | 34-45-14 | GDY0002 | S.. | 2 | | TB0130Y | | | FB | 153-154 |
| W1104 | 286T1104 | | | P19 INTEGRATION | | | | | | | | | | | |
| 001 | 20 | | PA | | 3-7 | 33-21-11 | T00180 | HV3 | E | | TB0146Z | 30 | BJ | | ALL |
| 002 | 20 | | PA | | 2-10 | 33-21-11 | D00092 | A2 | | | TB0146Z | 30 | BJ | | ALL |
| 003 | 24 | | PK | | 2-10 | 33-21-11 | D00092 | X1 | | | TB0146Z | 29 | BJ | | ALL |
| 004 | 24 | | PK | | 1-5 | 33-21-11 | D00092 | X2 | | | D13356 | B2 | | | 050-099, 150-199 |
| 004 | 24 | | PK | | 6-2 | 33-21-11 | D00092 | X2 | | | S01634 | 3 | C | | 275-299 |
| 005 | 24 | | PK | | 2-11 | 33-21-11 | D05110J | 14 | | | TB0146Z | 29 | BJ | | ALL |
| 006 | 20 | | PA | | 4-5 | 33-21-11 | D05110J | 17 | | | D00092 | A1 | | | 050-099 |
| 006 | 20 | | PA | | 2-10 | 33-21-11 | TB0146Y | C027 | BJ | | D00092 | A1 | | | 150-199 |
| 006 | 20 | | PA | | 6-7 | 33-21-11 | S01631 | 3 | C | * | D00092 | A1 | | | 275-299 |
| 007 | 20 | | PA | | 4-2 | 33-21-11 | D05912J | 5 | | | D00094 | A1 | | | 050-099 |
| 007 | 20 | | PA | | 3-2 | 33-21-11 | TB0146Y | A027 | BJ | | D00094 | A1 | | | 150-199 |
| 007 | 20 | | PA | | 6-11 | 33-21-11 | S01631 | 6 | C | * | D00094 | A1 | | | 275-299 |
| 008 | 20 | | PA | | 3-2 | 33-21-11 | TB0146Z | 30 | BJ | | D00094 | A2 | | | 050-099 |
| 008 | 20 | | PA | | 3-2 | 33-21-11 | D00094 | A2 | | | TB0146Z | 30 | BJ | | 150-199, 275-299 |
| 009 | 24 | | PK | | 3-2 | 33-21-11 | TB0146Z | 29 | BJ | | D00094 | X1 | | | ALL |
| 010 | 24 | | PK | | 3-3 | 33-21-11 | TB0146Y | C031 | BJ | | D13356 | X2 | | | 050-099 |
| 010 | 20 | | PA | | 3-3 | 33-21-11 | D13356 | X2 | | | TB0146Y | C031 | BJ | | 150-199 |
| 010 | 24 | | PK | | 6-5 | 33-21-11 | S01634 | 6 | C | | D00094 | X2 | | | 275-299 |
| 012 | 20 | | PA | | 3-2 | 33-21-11 | D00096 | A2 | | | TB0146Z | 30 | BJ | | 275-299 |
| 013 | 24 | | PK | | 3-2 | 33-21-11 | TB0146Z | 29 | BJ | | D00096 | X1 | | | 275-299 |
| 014 | 16 | | PA | | 2-10 | 33-21-31 | D05808J | 5 | | | TB0174G | 4 | 2 | | 150-154, 157-165, 167-199, 275-299 |
| 014 | 16 | | PQ | AN | 2-10 | 33-21-31 | D05808J | 5 | | | TB0174G | 4 | 2 | | 155-156, 166 |
| 014Z | | | | AN | 0-0 | 33-21-31 | D05808J | DED | | | TB0174G | DED | | | 155-156, 166 |
| 015 | 20 | | PA | | 6-11 | 33-21-11 | D00096 | A1 | | | S01631 | 1 | C | * | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 29

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|-------|---------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1104 | 286T1104 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 016 | 24 | | PK | | 6-5 | 33-21-11 | S01634 | | 1 | C | * | D00096 | X2 | | 275-299 |
| 01H | 20 | | PA | | 1-4 | 33-21-11 | S01632 | | 3 | C | | S01633 | 3 | C | 275-277, 280-299 |
| 01H | 20 | | PA | | 1-4 | 33-21-11 | S01632 | | 3 | C | * | S01633 | 3 | C | 278 |
| 020 | 20 | | PA | | 2-5 | 27-61-18 | D05134J | | 12 | | | TB0160F | C038 | 2 | ALL |
| 021 | 20 | | PA | | 1-7 | 33-21-11 | S01631 | | 1 | C | * | S01632 | 1 | C | 275-277, 280-299 |
| 021 | 20 | | PA | | 1-7 | 33-21-11 | S01631 | | 1 | C | * | S01632 | 1 | C | 278 |
| 022 | 20 | | PA | | 1-7 | 33-21-11 | S01631 | | 3 | C | * | S01632 | 3 | C | 275-299 |
| 023 | 20 | | PA | | 2-5 | 27-61-18 | D05134J | | 13 | | | TB0160F | C023 | 2 | ALL |
| 024 | 20 | | PA | | 4-5 | 33-21-11 | D00092 | | B1 | | | D05110J | 18 | | 050-099 |
| 024 | 20 | | PA | | 7-0 | 33-21-11 | D00092 | | B1 | | | SM09501 | 9 | | 275-277, 280-299 |
| 024 | 20 | | PA | | 4-5 | 33-21-11 | D00092 | | B1 | | | D05110J | 2 | | 278 |
| 025 | 20 | | PA | | 2-11 | 33-21-11 | D05110J | | 13 | | | TB0146Y | C027 | BJ | 150-199 |
| 025 | 20 | | PA | | 3-5 | 33-21-11 | D05110J | | 17 | | | S01632 | 3 | C | 275-299 |
| 026 | 20 | | PA | | 2-11 | 33-21-11 | TB0146Y | C027 | BJ | | | D05110J | 17 | | 150-199 |
| 027 | 22 | | PA | | 2-10 | 33-51-11 | D05808J | | 9 | | | TB0160Y | A014 | BJ | 050-099 |
| 027 | 22 | | PA | | 2-11 | 33-51-11 | D05110J | | 6 | | | TB0160Y | A014 | BJ | 150-199, 275-299 |
| 029 | 20 | | PA | | 7-0 | 33-21-11 | D05110J | | 2 | | | SM09501 | 9 | | 275-277, 280-299 |
| 030 | 24 | | PK | | 3-3 | 33-21-11 | D05110J | | 20 | | | S01634 | 1 | C | 275-299 |
| 032 | 20 | | PA | | 2-8 | 33-26-11 | TB0146Z | | 35 | BJ | | D05114J | 24 | | 050-099 |
| 032 | 22 | | PA | | 2-8 | 33-26-11 | D05114J | | 24 | | | TB0146Z | 35 | BJ | 150-199 |
| 032 | 20 | | PA | | 2-8 | 33-26-21 | D05114J | | 6 | | | TB0146Z | 35 | BJ | 275-299 |
| 033 | 20 | | PA | | 3-4 | 33-21-11 | D00100 | | A2 | | | TB0146Z | 30 | BJ | 275-299 |
| 034 | 24 | | PK | | 3-4 | 33-21-11 | TB0146Z | | 29 | BJ | | D00100 | X1 | | 275-299 |
| 035 | 24 | | PK | | 2-11 | 33-21-11 | D05110J | | 50 | | | TB0146Y | C031 | BJ | 050-099, 150-199 |
| 035 | 24 | | PK | | 6-8 | 33-21-11 | S01634 | | 4 | C | * | D00100 | X2 | | 275-299 |
| 036 | 20 | | PA | | 4-2 | 33-21-11 | D00094 | | B1 | | | D05912J | 7 | | 050-099 |
| 036 | 20 | | PA | | 2-5 | 33-21-11 | D05912J | | 7 | | | TB0146Y | C037 | BJ | 150-199 |
| 036 | 20 | | PA | | 7-1 | 33-21-11 | D00100 | | A1 | | | S01631 | 4 | C | 275-299 |
| 041 | 20 | | PA | | 1-7 | 33-21-11 | S01631 | | 4 | C | * | S01632 | 4 | C | 275-299 |
| 042 | 20 | | PA | | 2-5 | 33-21-11 | TB0146Y | A027 | BJ | | | D05912J | 5 | | 150-199 |
| 042 | 20 | | PA | | 3-6 | 33-21-11 | S01632 | | 6 | C | * | D05912J | 7 | | 275-299 |
| 043 | 20 | | PA | | 1-7 | 33-21-11 | S01631 | | 6 | C | * | S01632 | 6 | C | 275-299 |
| 045 | 20 | | PA | | 3-2 | 33-21-11 | D00094 | | B1 | | | TB0146Y | C037 | BJ | 150-199 |
| 045 | 20 | | PA | | 6-7 | 33-21-11 | D00094 | | B1 | | | S01633 | 6 | C | 275-299 |
| 046 | 20 | | PA | | 2-5 | 33-21-11 | D05912J | | 6 | | | TB0146Y | C037 | BJ | 150-199 |
| 050 | 24 | | PK | | 3-3 | 33-21-11 | D05110J | | 19 | | | S01634 | 4 | C | 275-299 |
| 051 | 16 | | PA | | 4-8 | 33-21-11 | D05134J | | 1 | | | T00180 | LV | E | ALL |
| 052 | 16 | | PA | | 2-8 | 33-21-11 | GDX0001 | | A.. | 2 | | T00180 | GND | E | ALL |
| 053 | 16 | | PA | | 3-10 | 33-21-12 | D05134J | | 2 | FL | | D05808J | 2 | | 050-099, 162-199 |

WIRE LIST
D280T132

91-21-11
Section W1100
Page 30
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|-----------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1104 | 286T1104 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 053 | 16 | | PA | 3-10 | 33-21-12 | D05134J | | 2 | | | | | D05808J | 2 | | | 150-157, 275-299 |
| 054 | 16 | | PA | 3-10 | 33-21-12 | D05134J | | 3 | FL | | | | D05808J | 1 | | | 050-099, 162-199 |
| 054 | 16 | | PA | 3-10 | 33-21-12 | D05134J | | 3 | | | | | D05808J | 1 | | | 150-157, 275-299 |
| 055 | 18 | | PA | 5-3 | 33-21-31 | D05134J | | 7 | FL | | | | T00183 | LV | E | * | 050-099 |
| 055 | 16 | | PA | 5-3 | 33-21-31 | D05134J | | 7 | | | | | T00183 | LV | E | * | 150-157, 275-299 |
| 055 | 16 | | PA | 5-3 | 33-21-31 | D05134J | | 29 | | | | | T00183 | LV | E | * | 162-199 |
| 056 | 18 | | PA | 5-0 | 33-21-31 | D05134J | | 8 | DL | | | | T00184 | LV | E | * | 050-099 |
| 056 | 16 | | PA | 5-0 | 33-21-31 | D05134J | | 8 | | | | | T00184 | LV | E | * | 150-157, 275-299 |
| 056 | 16 | | PA | 5-0 | 33-21-31 | D05134J | | 30 | | | | | T00184 | LV | E | * | 162-199 |
| 057 | 20 | | PA | 4-3 | 33-21-31 | T00183 | | | HV2 | E | | | TB0146Z | 25 | BJ | | 050-099, 150-154, 162, 275-278 |
| 057 | 20 | | PA | 4-3 | 33-21-31 | T00183 | | | HV2 | E | * | | TB0146Z | 25 | BJ | | 155-157, 163-199, 280-299 |
| 058 | 18 | | PA | 3-3 | 33-21-31 | T00183 | | | GND | E | | | GDX0001 | A.. | 2 | | 050-099 |
| 058 | 16 | | PA | 3-3 | 33-21-31 | T00183 | | | GND | E | | | GDX0001 | A.. | 2 | | 150-199, 275-299 |
| 059 | 20 | | PA | 2-5 | 33-21-31 | TB0146Z | | 25 | BJ | | | | D00106 | A2 | | | ALL |
| 060 | 20 | | PA | 2-5 | 33-21-31 | D00106 | | | B2 | | | | TB0146Z | 25 | BJ | | 050-099 |
| 060 | 20 | | PA | 2-5 | 33-21-31 | TB0146Z | | 25 | BJ | | | | D00106 | B2 | | | 150-199, 275-299 |
| 061 | 20 | | PA | 2-5 | 33-21-31 | D00104 | | | D2 | | | | TB0146Z | 25 | BJ | | 166 |
| 061 | 16 | | PA | 5-3 | 33-21-31 | T00183 | | | LV | E | * | | D00106 | C2 | | | 275-299 |
| 062 | 20 | | PA | 2-5 | 33-21-31 | TB0146Z | | 25 | BJ | | | | D00106 | D2 | | | ALL |
| 063 | 24 | | PK | 2-5 | 33-21-31 | TB0174Y | | | A006 | BJ | | | D00106 | X1 | | | ALL |
| 064 | 24 | | PK | 2-5 | 33-21-31 | D00106 | | | X2 | | | | TB0174Y | C012 | BJ | | 050-099 |
| 064 | 24 | | PK | 2-5 | 33-21-31 | D00106 | | | X2 | | | | TB0174X | A002 | BJ | | 150-157, 275-299 |
| 064 | 24 | | PK | 2-5 | 33-21-31 | D00106 | | | X2 | | | | TB0174Y | C013 | BJ | | 162-199 |
| 065 | 20 | | PA | 4-0 | 33-21-31 | D00106 | | | A1 | | | | D05110J | 25 | | | 050-099 |
| 065 | 20 | | PA | 3-9 | 33-21-31 | D00106 | | | A1 | | | | D05114J | 16 | | | 150-154, 157-165, 167-199 |
| 065 | 20 | | PA | 6-4 | 33-21-31 | D00106 | | | A1 | | | | S01635 | 3 | C | * | 275-299 |
| 066 | 24 | | PK | 2-10 | 33-21-12 | TB0174Y | | | C011 | BJ | | | D05808J | 7 | | | 155-157, 166-199 |
| 066 | 20 | | PA | 6-4 | 33-21-31 | D00106 | | | B1 | | | | S01635 | 6 | C | * | 275-299 |
| 067 | 16 | | PA | 6-3 | 33-21-31 | D00106 | | | C1 | | | | S01637 | 3 | C | * | 275-299 |
| 068 | 20 | | PA | 2-5 | 33-21-31 | D00106 | | | D1 | | | | TB0174Y | A012 | BJ | | 050-099, 150-199 |
| 068 | 20 | | PA | 6-4 | 33-21-31 | D00106 | | | D1 | | | | S01636 | 3 | C | * | 275-299 |
| 069 | 20 | | PA | 0-7 | 33-21-31 | S01635 | | 3 | C | * | | | S01636 | 6 | C | | 275-299 |
| 070 | 20 | | PA | 2-5 | 33-21-31 | D00106 | | | B1 | | | | TB0174Z | 10 | BJ | | 050-099, 150-199 |
| 071 | 16 | | PA | 3-6 | 33-21-31 | S01637 | | 3 | C | * | | | D05114J | 42 | | | 275-299 |
| 072 | 20 | | PA | 3-9 | 33-21-31 | S01637 | | 5 | C | | | | D05110J | 21 | | | 275-299 |
| 073 | 20 | | PA | 3-10 | 33-21-31 | S01635 | | 2 | C | | | | D05110J | 4 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 31

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1104 | 286T1104 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 074 | 20 | | | PA | 3-6 | 33-21-31 | D13372 | | A1 | | D05114J | | 17 | | 050-099, 162, 167-199 |
| 074 | 20 | | | PA | 2-8 | 33-21-31 | TB0174Z | | 10 | BJ | D05114J | | 17 | | 150-154, 157 |
| 074 | 20 | | | PQ | 2-8 | 33-21-31 | TB0174Z | | 10 | BJ | D05114J | | 17 | | 155-156 |
| 074 | 20 | | | PA | 3-6 | 33-21-31 | D05114J | | 17 | | D13372 | | A1 | | 163-165 |
| 074 | 20 | | | PA | 2-3 | 33-21-31 | D13372 | | A1 | | TB0146X | D042 | BJ | | 166 |
| 074 | 20 | | | PA | 1-5 | 33-21-31 | S01635 | | 1 | C | S01638 | | 4 | C | 275-299 |
| 074Z | | | | | 0-0 | 33-21-31 | TB0174Z | | DED | | D05114J | | DED | | 155-156 |
| 076 | 20 | | | PA | 1-4 | 33-21-31 | S01636 | | 3 | C | S01637 | | 6 | C | 275-299 |
| 077 | 20 | | | PA | 2-8 | 33-21-31 | TB0174Z | | 10 | BJ | D05114J | | 13 | | 050-099, 150-154, 157-165, 167-199 |
| 077 | 20 | | | PQ | 2-8 | 33-21-31 | TB0174Z | | 10 | BJ | D05114J | | 13 | | 155-156, 166 |
| 077 | 20 | | | PA | 1-4 | 33-21-31 | S01637 | | 4 | C | S01638 | | 1 | C | 275-299 |
| 077Z | | | | | 0-0 | 33-21-31 | TB0174Z | | DED | | D05114J | | DED | | 155-156, 166 |
| 079 | 20 | | | PA | 3-8 | 33-21-31 | S01638 | | 5 | C | D05110J | | 9 | | 275-299 |
| 080 | 20 | | | PA | 2-11 | 33-21-31 | D05110J | | 4 | | TB0174Z | | 10 | BJ | 150-154, 157-165, 167-199 |
| 080 | 20 | | | PQ | 2-11 | 33-21-31 | D05110J | | 4 | | TB0174Z | | 10 | BJ | 155-156, 166 |
| 080 | 20 | | | PA | 1-4 | 33-21-31 | S01636 | | 1 | C | S01637 | | 4 | C | 275-299 |
| 080Z | | | | | 0-0 | 33-21-31 | D05110J | | DED | | TB0174Z | | DED | | 155-156, 166 |
| 081 | 24 | | | PK | 2-11 | 33-21-12 | TB0174Y | | A005 | BJ | D05110J | | 45 | | 050-099 |
| 081 | 24 | | | PK | 2-11 | 33-21-12 | D05110J | | 45 | | TB0174Y | A005 | BJ | | 150-199 |
| 082 | 20 | | | PA | 2-8 | 33-21-31 | TB0174Y | | A018 | BJ | D05114J | | 42 | | 150-154, 157-165, 167-199 |
| 082 | 20 | | | PQ | 2-8 | 33-21-31 | TB0174Y | | A018 | BJ | D05114J | | 42 | | 155-156, 166 |
| 082Z | | | | | 0-0 | 33-21-31 | TB0174Y | | DED | | D05114J | | DED | | 155-156, 166 |
| 083 | 24 | | | PK | 2-11 | 33-21-12 | TB0174Y | | A005 | BJ | D05110J | | 56 | | 050-099 |
| 083 | 24 | | | PK | 2-11 | 33-21-12 | D05110J | | 56 | | TB0174Y | A005 | BJ | | 150-199 |
| 084 | 20 | | | PA | 3-7 | 33-21-31 | S01635 | | 6 | C | D05114J | | 17 | | 275-299 |
| 085 | 20 | | | PA | 3-7 | 33-21-31 | S01635 | | 5 | C | D05114J | | 13 | | 275-299 |
| 086 | 20 | | | PA | 2-8 | 33-21-31 | D05114J | | 9 | | TB0174Y | A012 | BJ | | 050-099 |
| 086 | 20 | | | PA | 2-8 | 33-21-31 | TB0174Y | | A012 | BJ | D05114J | | 9 | | 150-154, 157-165, 167-199 |
| 086 | 20 | | | PQ | 2-8 | 33-21-31 | TB0174Y | | A012 | BJ | D05114J | | 9 | | 155-156, 166 |
| 086 | 20 | | | PA | 3-7 | 33-21-31 | S01636 | | 5 | C | D05114J | | 16 | | 275-299 |
| 086Z | | | | | 0-0 | 33-21-31 | D05114J | | DED | | TB0174Y | | DED | | 155-156, 166 |
| 087 | 20 | | | PA | 2-11 | 33-21-31 | D05110J | | 21 | | TB0174Y | A012 | BJ | | 150-154, 157-165, 167-199 |
| 087 | 20 | | | PQ | 2-11 | 33-21-31 | D05110J | | 21 | | TB0174Y | A012 | BJ | | 155-156, 166 |
| 087 | 20 | | | PA | 3-10 | 33-21-31 | D05110J | | 7 | | S01635 | | 6 | C | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 32

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1104 | 286T1104 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 087Z | | | | DL | 0-0 | 33-21-31 | D05110J | | DED | | | | TB0174Y | DED | | | 155-156, 166 |
| 089 | 20 | PA | | | 2-11 | 33-21-31 | D05110J | | 10 | | | | TB0174Z | 10 | BJ | | 050-099, 150-154, 157-165, 167-199 |
| 089 | 20 | PQ | DN | | 2-11 | 33-21-31 | D05110J | | 10 | | | | TB0174Z | 10 | BJ | | 155-156, 166 |
| 089 | 16 | PA | | | 3-6 | 33-21-31 | D05114J | | 15 | | | | S01637 | 2 | C | | 275-278 |
| 089 | 16 | PA | | | 3-6 | 33-21-31 | D05114J | | 15 | | | | S01637 | 2 | C | * | 280-299 |
| 089Z | | | DN | | 0-0 | 33-21-31 | D05110J | | DED | | | | TB0174Z | DED | | | 155-156, 166 |
| 090 | 18 | PA | | | 3-11 | 33-21-31 | D00104 | | A1 | | | | D05110J | 6 | DK | | 050-099 |
| 090 | 16 | PA | | | 2-5 | 33-21-31 | D00104 | | A1 | | | | TB0174G | 4 | 2 | | 150-199, 275-278 |
| 090 | 16 | PA | | | 6-3 | 33-21-31 | D00104 | | A1 | | | | S01637 | 1 | C | | 280-299 |
| 091 | 20 | PA | | | 6-4 | 33-21-31 | D00104 | | B1 | | | | S01635 | 4 | C | * | 275-299 |
| 092 | 20 | PA | | | 3-8 | 33-21-31 | D00104 | | C1 | | | | D05114J | 11 | | | 050-099 |
| 092 | 20 | PA | | | 2-5 | 33-21-31 | D00104 | | C1 | | | | TB0174Y | A018 | BJ | | 150-199 |
| 092 | 20 | PA | | | 6-4 | 33-21-31 | D00104 | | C1 | | | | S01635 | 1 | C | * | 275-299 |
| 093 | 20 | PA | | | 6-4 | 33-21-31 | D00104 | | D1 | | | | S01636 | 1 | C | * | 275-299 |
| 094 | 18 | PA | | | 5-2 | 33-21-31 | D00104 | | A2 | | | | T00183 | LV | E | * | 050-099 |
| 094 | 16 | PA | | | 5-2 | 33-21-31 | D00104 | | A2 | | | | T00183 | LV | E | * | 150-199, 280-299 |
| 094 | 16 | PA | | | 4-11 | 33-21-31 | D00104 | | A2 | | | | T00184 | LV | E | * | 275-278 |
| 095 | 20 | PA | | | 2-5 | 33-21-31 | D00104 | | B2 | | | | TB0174Z | 9 | BJ | | 050-099 |
| 095 | 20 | PA | | | 2-5 | 33-21-31 | D00104 | | B2 | | | | TB0146Z | 25 | BJ | | 150-199, 275-299 |
| 096 | 20 | PA | | | 2-5 | 33-21-31 | D00104 | | C2 | | | | TB0146Z | 25 | BJ | | ALL |
| 097 | 20 | PA | | | 2-5 | 33-21-31 | D00104 | | D2 | | | | TB0146Z | 25 | BJ | | 150-165, 167-199, 275-299 |
| 098 | 20 | PA | | | 3-11 | 33-21-31 | T00184 | | HV2 | E | | | TB0174Z | 9 | BJ | | ALL |
| 099 | 18 | PA | | | 3-0 | 33-21-31 | T00184 | | GND | E | | | GDX0001 | A.. | 2 | | 050-099 |
| 099 | 16 | PA | | | 3-0 | 33-21-31 | T00184 | | GND | E | | | GDX0001 | A.. | 2 | | 150-199, 275-299 |
| 100 | 24 | PK | | | 2-5 | 33-21-31 | D00104 | | X1 | | | | TB0174Y | A006 | BJ | | ALL |
| 101 | 24 | PK | | | 2-5 | 33-21-31 | D00104 | | X2 | | | | TB0174Y | C006 | BJ | | 275-278 |
| 101 | 24 | PK | | | 2-5 | 33-21-31 | D00104 | | X2 | | | | TB0174X | D001 | BJ | | 280-299 |
| 102 | 22 | PA | | | 2-8 | 33-24-11 | D05114J | | 19 | | | | TB0146Y | C016 | BJ | | 050-099 |
| 102 | 22 | PA | | | 2-8 | 33-24-11 | D05114J | | 1 | | | | TB0146Y | C016 | BJ | | 150-199, 275-299 |
| 103 | 20 | PA | | | 2-11 | 33-21-31 | TB0174Y | | A018 | BJ | | | D05110J | 25 | | | 150-154, 157-165, 167-199 |
| 103 | 20 | PQ | EC | | 2-11 | 33-21-31 | TB0174Y | | A018 | BJ | | | D05110J | 25 | | | 155-156, 166 |
| 103 | 20 | PA | | | 0-7 | 33-21-31 | S01635 | | 4 | C | * | | S01636 | 4 | C | | 275-299 |
| 103Z | | | EC | | 0-0 | 33-21-31 | TB0174Y | | DED | | | | D05110J | DED | | | 155-156, 166 |
| 107 | 22 | PA | | | 2-5 | 33-51-21 | TB0160Y | | A012 | BJ | | | D05134J | 17 | | | 050-099 |
| 107 | 22 | PA | | | 2-5 | 33-51-21 | D05134J | | 17 | | | | TB0160Y | A012 | BJ | | 150-199, 275-299 |
| 108 | 22 | PA | | | 2-5 | 33-51-21 | TB0160Y | | C013 | BJ | | | D05134J | 18 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 33

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|------|----|--|---|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W1104 | 286T1104 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | | | |
| 108 | 22 | | PA | | 2-5 | 33-51-21 | D05134J | | | | 18 | | | | TB0160Y | C013 | BJ | | 150-199, 275-299 |
| 114 | 22 | | PA | | 2-8 | 33-26-11 | D05114J | | | | 2 | | | | TB0174Z | 36 | BJ | | 150-199 |
| 114 | 22 | | PA | | 2-8 | 33-26-11 | D05114J | | | | 2 | | | | TB0146Y | C006 | BJ | | 275-299 |
| 115 | 20 | | PA | | 2-11 | 33-26-11 | D05110J | | | | 3 | | | | TB0146Z | 36 | BJ | | ALL |
| 116 | 16 | | PA | | 3-9 | 38-13-11 | D05134J | | | | 11 | FL | | | D05114J | 23 | FM | | 050-099 |
| 116 | 16 | | PA | | 3-9 | 38-13-11 | D05134J | | | | 11 | | | | D05114J | 41 | | | 150-157 |
| 116 | 16 | | PA | | 3-9 | 38-13-11 | D05134J | | | | 31 | | | | D05114J | 41 | | | 162-199 |
| 116 | 16 | | PA | | 2-8 | 38-13-11 | TB0174G | | | | 31 | 2 | | | D05114J | 41 | | | 275-299 |
| 117 | 22 | | PA | | 2-5 | 33-22-11 | D05134J | | | | 10 | | | | TB0174X | A001 | BJ | | 050-099 |
| 117 | 20 | | PA | | 2-5 | 33-22-11 | D05134J | | | | 10 | | | | TB0174X | A001 | BJ | | 150-154, 157-165, 167-199, 275-299 |
| 117 | 20 | | PQ | EQ | 2-5 | 33-22-11 | D05134J | | | | 10 | | | | TB0174X | A001 | BJ | | 155-156, 166 |
| 117Z | | | | EQ | 0-0 | 33-22-11 | D05134J | | | | DED | | | | TB0174X | DED | | | 155-156, 166 |
| 118 | 16 | | PA | | 3-9 | 38-13-11 | D05134J | | | | 16 | FL | | | D05114J | 21 | FM | | 050-099 |
| 118 | 16 | | PA | | 3-9 | 38-13-11 | D05134J | | | | 16 | | | | D05114J | 40 | | | 150-157 |
| 118 | 16 | | PA | | 3-9 | 38-13-11 | D05134J | | | | 34 | | | | D05114J | 31 | | | 162-199 |
| 118 | 16 | | PA | | 2-8 | 38-13-11 | TB0174G | | | | 31 | 2 | | | D05114J | 43 | | | 275-299 |
| 119 | 20 | | PA | | 2-5 | 33-44-11 | D05134J | | | | 14 | | | | TB0146F | A003 | 2 | | ALL |
| 121 | 16 | | PA | | 2-3 | 33-21-31 | D13372 | | | | B1 | | | | TB0146F | A047 | 2 | | 166 |
| 121 | 22 | | PA | | 2-8 | 33-26-21 | D05114J | | | | 10 | | | | TB0146Z | 35 | BJ | | 275-278 |
| 121 | 20 | | PA | | 2-8 | 33-26-21 | D05114J | | | | 31 | | | | TB0146X | D008 | BJ | | 280-299 |
| 122 | 20 | | PA | | 2-5 | 33-21-11 | D05912J | | | | 4 | | | | TB0146Y | A027 | BJ | | 150-199 |
| 122 | 20 | | PA | | 3-5 | 33-21-11 | S01633 | | | | 6 | C | * | | D05912J | 3 | | | 275-299 |
| 123 | 20 | | PA | | 2-11 | 33-21-31 | TB0174Y | | | | C012 | BJ | | | D05110J | 26 | | | 150-154, 157-165, 167-199, 275-299 |
| 123 | 20 | | PQ | EW | 2-11 | 33-21-31 | TB0174Y | | | | C012 | BJ | | | D05110J | 26 | | | 155-156, 166 |
| 123Z | | | | EW | 0-0 | 33-21-31 | TB0174Y | | | | DED | | | | D05110J | DED | | | 155-156, 166 |
| 124 | 20 | | PA | | 2-8 | 33-21-31 | TB0174Y | | | | C012 | BJ | | | D05114J | 18 | | | 150-154, 157-165, 167-199, 275-299 |
| 124 | 20 | | PQ | EX | 2-8 | 33-21-31 | TB0174Y | | | | C012 | BJ | | | D05114J | 18 | | | 155-156, 166 |
| 124Z | | | | EX | 0-0 | 33-21-31 | TB0174Y | | | | DED | | | | D05114J | DED | | | 155-156, 166 |
| 125 | 22 | | PA | | 2-10 | 33-27-11 | D02894 | | | | X1 | | | | TB0174Z | 29 | BJ | | ALL |
| 126 | 22 | | PA | | 3-6 | 33-27-11 | D02892 | | | | X1 | | | | TB0174Z | 29 | BJ | | ALL |
| 127 | 20 | | PA | | 2-10 | 33-27-11 | D02894 | | | | B2 | | | | TB0146Z | 26 | BJ | | 050-099, 150-154, 157-165, 167-199, 275-299 |
| 127 | 20 | | PQ | FB | 2-10 | 33-27-11 | D02894 | | | | B2 | | | | TB0146Z | 26 | BJ | | 155-156, 166 |
| 127Z | | | | FB | 0-0 | 33-27-11 | D02894 | | | | DED | | | | TB0146Z | DED | | | 155-156, 166 |
| 128 | 20 | | PA | | 6-9 | 33-21-11 | D00100 | | | | B1 | | | | S01633 | 4 | C | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1100
Page 34
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1104 | 286T1104 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 129 | 22 | | PA | | 2-10 | 33-27-11 | D02894 | | X2 | | | | TB0146X | C007 | BJ | | ALL |
| 130 | 20 | | PA | | 3-6 | 33-27-11 | D02892 | | B2 | | | | TB0146Z | 26 | BJ | | 050-099, 150-154, 157-165, 167-199, 275-299 |
| 130 | 20 | PQ | FE | | 3-6 | 33-27-11 | D02892 | | B2 | | | | TB0146Z | 26 | BJ | | 155-156, 166 |
| 130Z | | | FE | | 0-0 | 33-27-11 | D02892 | | DED | | | | TB0146Z | DED | | | 155-156, 166 |
| 131 | 22 | PA | | | 3-6 | 33-27-11 | D02892 | | X2 | | | | TB0146X | B008 | BJ | | ALL |
| 133 | 20 | PA | | | 2-10 | 33-27-11 | TB0174Z | | 29 | BJ | | | D02894 | A2 | | | 162-199 |
| 136 | 20 | PA | | | 3-6 | 33-27-11 | TB0174Z | | 29 | BJ | | | D02892 | A2 | | | 162-199 |
| 138 | 20 | PA | | | 2-10 | 33-27-11 | D02894 | | B1 | | | | D05134J | 6 | | | 050-099, 150-154, 157-165, 167-199, 275-299 |
| 138 | 20 | PQ | FM | | 2-10 | 33-27-11 | D02894 | | B1 | | | | D05134J | 6 | | | 155-156, 166 |
| 138Z | | | FM | | 0-0 | 33-27-11 | D02894 | | DED | | | | D05134J | DED | | | 155-156, 166 |
| 139 | 20 | PA | | | 3-6 | 33-27-11 | D02892 | | B1 | | | | D05134J | 9 | | | 050-099, 150-154, 157-165, 167-199, 275-299 |
| 139 | 20 | PQ | FN | | 3-6 | 33-27-11 | D02892 | | B1 | | | | D05134J | 9 | | | 155-156, 166 |
| 139Z | | | FN | | 0-0 | 33-27-11 | D02892 | | DED | | | | D05134J | DED | | | 155-156, 166 |
| 145 | 22 | PA | | | 2-5 | 33-22-41 | D05134J | | 15 | | | | TB0174X | C002 | BJ | | ALL |
| 146 | 20 | PA | | | 4-3 | 33-21-31 | T00183 | | HV2 | E | | | TB0146Z | 26 | BJ | | 050-099, 150-154, 162, 275-278 |
| 146 | 20 | PA | | | 4-3 | 33-21-31 | T00183 | | HV2 | E | * | | TB0146Z | 26 | BJ | | 155-157, 163-199, 280-299 |
| 149 | 22 | PA | | | 2-8 | 33-26-11 | D05114J | | 4 | | | | TB0146Y | C006 | BJ | | ALL |
| 152 | 20 | PA | | | 3-6 | 33-21-11 | S01632 | | 5 | C | | | D05912J | 6 | | | 275-299 |
| 155 | 20 | PA | | | 3-5 | 33-21-11 | S01632 | | 2 | C | | | D05110J | 13 | | | 275-299 |
| 157 | 20 | PA | | | 3-8 | 33-21-31 | S01638 | | 2 | C | * | | D05110J | 25 | | | 275-299 |
| 158 | 20 | PA | | | 3-10 | 33-21-31 | S01635 | | 6 | C | * | | D05110J | 10 | | | 275-299 |
| 160 | 20 | PA | | | 3-11 | 33-21-31 | D00104 | | B1 | | | | D05110J | 8 | | | 050-099 |
| 160 | 20 | PA | | | 3-8 | 33-21-31 | D00104 | | B1 | | | | D05114J | 21 | | | 150-154, 157-165, 167-199 |
| 160 | 20 | PA | | | 3-5 | 33-21-31 | S01638 | | 2 | C | * | | D05114J | 21 | | | 275-299 |
| 162 | 20 | PA | | | 3-7 | 33-21-31 | S01636 | | 2 | C | | | D05114J | 9 | | | 275-299 |
| 164 | 24 | PK | | | 3-3 | 33-21-11 | S01634 | | 2 | C | | | D05110J | 5 | | | 275-299 |
| 165 | 20 | PA | | | 2-10 | 33-21-11 | D00092 | | B2 | | | | TB0146Z | 30 | BJ | | 050-099, 150-199 |
| 165 | 20 | PA | | | 3-2 | 33-21-11 | D00096 | | B2 | | | | TB0146Y | C028 | BJ | | 275-277, 280-299 |
| 165 | 20 | PA | | | 3-2 | SPARE | D00096 | | B2 | | | | TB0146Y | C028 | BJ | | 278 |
| 193 | 22 | PA | | | 2-5 | 33-51-11 | TB0160Y | | A014 | BJ | | | D05134J | 5 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 35

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1104 | 286T1104 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 202B | 22 | PB | B | 2-8 | 23-31-14 | D05114J | 26 | | | TB0174Y | C025 | BJ | | 275-299 | |
| 202R | 22 | PB | B | 0-0 | 23-31-14 | D05114J | 25 | | | TB0174Y | A025 | BJ | | 275-299 | |
| 500 | 24 | PK | | 2-7 | 33-21-31 | D13370 | X2 | | | TB0174X | D001 | BJ | | 050-099, 150-199 | |
| 501 | 16 | PA | | 2-5 | 38-13-11 | D05134J | 11 | | | TB0174G | 31 | 2 | | 275-299 | |
| 505 | 16 | PA | | 2-8 | 33-21-31 | TB0174G | 3 | 2 | | D05114J | 28 | | | 162-165, 167-199 | |
| 505 | 16 | PQ | UE | 2-8 | 33-21-31 | TB0174G | 3 | 2 | | D05114J | 28 | | | 166 | |
| 505Z | | | UE | 0-0 | 33-21-31 | TB0174G | DED | | | D05114J | DED | | | 166 | |
| 525 | 20 | PA | | 2-6 | 33-21-31 | D10766 | A1 | | | TB0174Y | C012 | BJ | | 150-199, 275-299 | |
| 526 | 16 | PA | | 2-10 | 33-21-31 | D05808J | 4 | | | TB0174G | 4 | 2 | | 150-154, 157-165, 167-199, 275-299 | |
| 526 | 16 | PQ | VA | 2-10 | 33-21-31 | D05808J | 4 | | | TB0174G | 4 | 2 | | 155-156, 166 | |
| 526Z | | | VA | 0-0 | 33-21-31 | D05808J | DED | | | TB0174G | DED | | | 155-156, 166 | |
| 532 | 20 | PA | | 2-11 | 33-21-11 | D05110J | 18 | | | TB0146Y | C028 | BJ | | 150-199 | |
| 532 | 20 | PA | | 2-8 | 33-21-11 | D05114J | 5 | | | TB0146Y | C028 | BJ | | 275-299 | |
| 551 | 16 | PA | | 2-8 | 33-21-31 | D05114J | 27 | | | TB0174G | 4 | 2 | | 150-154, 157-165, 167-199, 275-299 | |
| 551 | 16 | PQ | WA | 2-8 | 33-21-31 | D05114J | 27 | | | TB0174G | 4 | 2 | | 155-156, 166 | |
| 551Z | | | WA | 0-0 | 33-21-31 | D05114J | DED | | | TB0174G | DED | | | 155-156, 166 | |
| 561 | 20 | PA | | 2-8 | 33-24-11 | D05114J | 39 | | | TB0174Y | A013 | BJ | | 275-299 | |
| 567 | 20 | PA | | 3-5 | 33-21-11 | S01633 | 5 | C | | D05912J | 4 | | | 275-299 | |
| 575 | 18 | PA | | 4-0 | 33-21-31 | D05110J | 9 | DK | | D10766 | B1 | | | 050-099 | |
| 575 | 16 | PA | | 3-9 | 33-21-31 | D10766 | B1 | | | D05114J | 28 | FM | | 150-154 | |
| 575 | 16 | PA | | 2-6 | 33-21-31 | D10766 | B1 | | | TB0160F | A023 | 2 | | 155-156 | |
| 575 | 16 | PA | | 3-9 | 33-21-31 | D10766 | B1 | | | D05114J | 28 | | | 157 | |
| 575 | 16 | PA | | 2-6 | 33-21-31 | D10766 | B1 | | | TB0174G | 3 | 2 | | 162-199 | |
| 575 | 16 | PA | | 6-4 | 33-21-31 | D10766 | B1 | | | S01637 | 1 | C | | 275-278 | |
| 575 | 16 | PA | | 2-6 | 33-21-31 | D10766 | B1 | | | TB0174G | 4 | 2 | | 280-299 | |
| 576 | 24 | PK | | 2-6 | 33-21-31 | TB0174Y | A006 | BJ | | D10766 | X1 | | | 050-099 | |
| 576 | 24 | PK | | 2-6 | 33-21-31 | D10766 | X1 | | | TB0174Y | A006 | BJ | | 150-199, 275-299 | |
| 586 | 20 | PA | | 2-6 | 33-21-31 | D10766 | A2 | | | TB0174Z | 9 | BJ | | 150-165, 167-199, 275-299 | |
| 586 | 20 | PQ | XK | 2-11 | 33-21-31 | D05110J | 11 | | | TB0174Z | 9 | BJ | | 166 | |
| 586Z | | | XK | 0-0 | 33-21-31 | TB0174Z | DED | | | D05110J | DED | | | 166 | |
| 587 | 20 | PA | | 2-6 | 33-21-31 | TB0174Z | 9 | BJ | | D10766 | C2 | | | 050-099, 163-199, 280-299 | |
| 587 | 20 | PA | | 2-6 | 33-21-31 | D10766 | C2 | | | TB0174Z | 9 | BJ | | 150-162, 275-278 | |
| 588 | 24 | PK | | 2-11 | 33-21-12 | TB0174Y | C006 | BJ | | D05110J | 44 | | | 050-099 | |
| 588 | 24 | PK | | 2-11 | 33-21-12 | D05110J | 44 | | | TB0174Y | C006 | BJ | | 150-199 | |
| 588 | 24 | PK | | 2-6 | 33-21-31 | D10766 | X2 | | | TB0174Y | C006 | BJ | | 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 36

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1104 | 286T1104 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | | |
| 590 | 22 | | PA | | 2-8 | 33-25-11 | D05114J | | 20 | | | | | TB0146Y | A005 | BJ | | 275-299 |
| 591 | 18 | | PA | | 2-8 | 26-13-11 | D05114J | | 34 | | | | | TB0174H | 3 | 2 | | 050-099 |
| 591 | 18 | | PA | | 2-8 | 26-13-11 | TB0174G | | 3 | 2 | | | | D05114J | 19 | DK | | 150-157 |
| 591 | 22 | | PA | | 2-8 | 33-25-11 | D05114J | | 7 | | | | | TB0146Y | C005 | BJ | | 275-299 |
| 592 | 22 | | PA | | 2-8 | 33-26-11 | D05114J | | 22 | | | | | TB0146Z | 36 | BJ | | 275-299 |
| 593 | 22 | | PA | | 2-8 | 33-26-11 | TB0146Y | | C006 | BJ | | | | D05114J | 3 | | | 050-099 |
| 593 | 22 | | PA | | 2-8 | 33-26-11 | D05114J | | 3 | | | | | TB0146Z | 36 | BJ | | 150-199 |
| 593 | 22 | | PA | | 2-8 | 33-26-11 | D05114J | | 3 | | | | | TB0146Y | C006 | BJ | | 275-299 |
| 594 | 20 | | PA | | 2-8 | 33-26-11 | D05114J | | 24 | | | | | TB0146Y | A028 | BJ | | 275-299 |
| 596 | 20 | | PA | | 2-5 | 33-21-11 | T00180 | | HV2 | E | | | | D05114J | 5 | | | 050-099 |
| 596 | 20 | | PA | | 2-11 | 33-21-11 | TB0146Y | | C028 | BJ | | | | D05110J | 16 | | | 150-199 |
| 596 | 20 | | PA | | 3-7 | 33-21-11 | T00180 | | HV2 | E | * | | | TB0146Y | C028 | BJ | | 275-299 |
| 598 | 20 | | PA | | 3-2 | 33-21-11 | D00094 | | B2 | | | | | TB0146Z | 30 | BJ | | 050-099, 150-199 |
| 598 | 20 | | PA | | 3-4 | 33-21-11 | D00100 | | B2 | | | | | TB0146Y | C028 | BJ | | 275-299 |
| 599 | 24 | | PK | | 2-7 | 33-21-31 | D13370 | | X1 | | | | | TB0174Z | 37 | BJ | | 050-099, 150-199 |
| 600 | 22 | | PA | | 2-5 | 33-21-21 | TB0174X | | B001 | BJ | | | | D05134J | 19 | | | 050-099, 150-199, 275-276 |
| 600 | 22 | | PA | | 2-5 | 33-21-21 | D05134J | | 19 | | | | | TB0174X | B001 | BJ | | 277-299 |
| 601 | 20 | | PA | | 2-8 | 26-13-11 | D05114J | | 20 | | | | | TB0174X | C001 | BJ | | 050-099, 150-199 |
| 602 | 20 | | PA | | 2-8 | 33-26-21 | D05114J | | 28 | | | | | TB0146X | B007 | BJ | | 275-299 |
| 603 | 20 | | PA | | 4-3 | 33-21-31 | T00183 | | HV2 | E | | | | TB0174Y | C005 | BJ | | 150-154, 162 |
| 603 | 20 | | PA | | 4-3 | 33-21-31 | T00183 | | HV2 | E | * | | | TB0174Y | C005 | BJ | | 155-157, 163-199 |
| 603 | 20 | | PA | | 2-6 | 33-21-31 | D10766 | | C1 | | | | | TB0174Y | C005 | BJ | | 275-299 |
| 604 | 20 | | PA | | 4-0 | 33-21-31 | D10766 | | D1 | | | | | D05110J | 5 | | | 050-099 |
| 604 | 20 | | PA | | 4-0 | 33-21-31 | D10766 | | D1 | | | | | D05110J | 15 | | | 150-154, 157-165, 167-199, 275-299 |
| 605 | 20 | | PA | | 2-6 | 33-21-31 | D10766 | | D2 | | | | | TB0174Z | 9 | BJ | | ALL |
| 608 | 20 | | PA | | 2-11 | 33-21-31 | TB0174Y | | C012 | BJ | | | | D05110J | 40 | | | 162-165, 167-199 |
| 608 | 20 | | PQ | YH | 2-11 | 33-21-31 | TB0174Y | | C012 | BJ | | | | D05110J | 40 | | | 166 |
| 608Z | | | | YH | 0-0 | 33-21-31 | TB0174Y | | DED | | | | | D05110J | DED | | | 166 |
| 609 | 20 | | PA | | 2-3 | 33-21-31 | D13372 | | A2 | | | | | TB0146Z | 26 | BJ | | 050-099 |
| 609 | 20 | | PA | | 2-3 | 33-21-31 | TB0174Y | | C005 | BJ | | | | D13372 | A2 | | | 150-199 |
| 609 | 20 | | PA | | 2-8 | 33-21-31 | TB0174Y | | C005 | BJ | | | | D05114J | 11 | | | 275-299 |
| 610 | 20 | | PA | | 2-7 | 33-21-31 | D13370 | | A2 | | | | | TB0146Z | 26 | BJ | | 050-099 |
| 610 | 20 | | PA | | 2-7 | 33-21-31 | TB0174Y | | C005 | BJ | | | | D13370 | A2 | | | 150-199 |
| 610 | 20 | | PA | | 2-11 | 33-21-31 | TB0174Y | | C005 | BJ | | | | D05110J | 8 | | | 275-299 |
| 611 | 20 | | PA | | 2-8 | 33-21-31 | D05114J | | 12 | | | | | TB0174Y | C005 | BJ | | 275-299 |
| 614 | 20 | | PA | | 3-10 | 33-21-11 | S01631 | | 5 | C | | | | D05912J | 5 | | | 275-299 |
| 616 | 20 | | PA | | 3-8 | 33-21-11 | D05110J | | 18 | | | | | S01631 | 2 | C | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 37

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1104 | 286T1104 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 618 | 20 | | PA | | 5-4 | 33-21-11 | D00094 | | B2 | | T00180 | HV2 | E | * | 275-299 |
| 619 | 20 | | PA | | 2-5 | 33-21-11 | D05114J | | 5 | | T00180 | HV2 | E | | 150-199 |
| 619 | 20 | | PA | | 5-1 | 33-21-11 | D00092 | | B2 | | T00180 | HV2 | E | * | 275-299 |
| 621 | 20 | | PA | | 1-4 | 33-21-11 | S01632 | | 1 | C | S01633 | 1 | C | | 275-277, 280-299 |
| 621 | 20 | | PA | | 1-4 | 33-21-11 | S01632 | | 1 | C | S01633 | 1 | C | * | 278 |
| 627 | 18 | | PA | | 5-0 | 33-21-31 | D10766 | | B2 | | T00184 | LV | E | * | 050-099 |
| 627 | 16 | | PA | | 5-0 | 33-21-31 | T00184 | | LV | E | D10766 | B2 | | | 150-165, 280-299 |
| 627 | 16 | | PA | | 5-0 | 33-21-31 | D10766 | | B2 | | T00184 | LV | E | * | 166-199 |
| 627 | 16 | | PA | | 5-3 | 33-21-31 | T00183 | | LV | E | D10766 | B2 | | | 275-278 |
| 628 | 20 | | PA | | 3-4 | 33-21-11 | S01633 | | 2 | C | D05110J | 12 | | | 275-299 |
| 635 | 24 | | PK | | 3-3 | 33-21-11 | S01634 | | 5 | C | D05110J | 23 | | | 275-299 |
| 639 | 22 | | PA | | 2-11 | 33-22-41 | D05110J | | 53 | | TB0146F | A024 | 2 | | 050-099, 150-199 |
| 642 | 20 | | PA | | 1-4 | 33-21-31 | S01637 | | 6 | C | S01638 | 6 | C | * | 275-299 |
| 643 | 22 | | PA | | 2-11 | 33-22-41 | D05110J | | 54 | | TB0146F | C024 | 2 | | 050-099, 150-199 |
| 644 | 20 | | PA | | 0-7 | 33-21-31 | S01638 | | 3 | C | S01638 | 6 | C | * | 275-299 |
| 645 | 24 | | PK | | 2-11 | 33-21-12 | TB0174Y | | C006 | BJ | D05110J | 55 | | | 050-099 |
| 645 | 24 | | PK | | 2-11 | 33-21-12 | D05110J | | 55 | | TB0174Y | C006 | BJ | | 150-199 |
| 647 | 24 | | PK | | 3-3 | 33-21-11 | D13356 | | A3 | | TB0160X | B005 | BJ | | 050-099, 150-199 |
| 648 | 24 | | PK | | 3-3 | 33-21-11 | D13356 | | B3 | | TB0160X | C005 | BJ | | 050-099, 150-199 |
| 650 | 24 | | PK | | 3-3 | 33-21-11 | D13356 | | Y2 | | TB0146Y | C002 | BJ | | 050-099, 150-199 |
| 651 | 20 | | PA | | 2-11 | 33-26-11 | D05110J | | 43 | | TB0146Y | C001 | BJ | | 050-099 |
| 652 | 20 | | PA | | 2-8 | 33-26-11 | TB0146Y | | C001 | BJ | D05114J | 22 | | | 050-099 |
| 652 | 20 | | PA | | 2-8 | 33-26-11 | D05114J | | 22 | | TB0146Y | C001 | BJ | | 150-199 |
| 655 | 20 | | PA | | 2-8 | 33-24-11 | D05114J | | 40 | | TB0174Z | 38 | BJ | | 275-299 |
| 664 | 24 | | PK | | 2-3 | 33-21-31 | D13372 | | X1 | | TB0174Z | 37 | BJ | | 050-099, 150-199 |
| 665 | 24 | | PK | | 2-11 | 33-21-11 | D05110J | | 48 | | TB0174Z | 37 | BJ | | 050-099, 150-199 |
| 700 | 20 | | PA | | 3-11 | 33-21-31 | D00104 | | D1 | | D05110J | 9 | | | 150-154, 157-165, 167-199 |
| 705 | 16 | | PA | | 3-9 | 33-21-31 | S01637 | | 2 | C | D05110J | 27 | | | 280-299 |
| 706 | 18 | | PA | | 2-8 | 26-13-11 | TB0174H | | 39 | 2 | D05114J | 19 | DK | | 162-199 |
| 717 | 20 | | PA | | 3-9 | 33-21-31 | D10766 | | C1 | | D05114J | 12 | | | 050-099, 150-154, 157-165, 167-199 |
| 718 | 24 | | PK | | 4-9 | 33-21-11 | D05110J | | 46 | | D13356 | A1 | | | 050-099 |
| 718 | 24 | | PK | | 4-9 | 33-21-11 | D13356 | | A1 | | D05110J | 46 | | | 150-199 |
| 719 | 24 | | PK | | 4-9 | 33-21-11 | D05110J | | 47 | | D13356 | B1 | | | 050-099 |
| 719 | 24 | | PK | | 4-9 | 33-21-11 | D13356 | | B1 | | D05110J | 47 | | | 150-199 |
| 720 | 24 | | PK | | 3-3 | 33-21-11 | D13356 | | D3 | | TB0160X | D005 | BJ | | 050-099, 150-199 |
| 721 | 24 | | PK | | 4-9 | 33-21-11 | D05110J | | 49 | | D13356 | D1 | | | 050-099 |
| 721 | 24 | | PK | | 4-9 | 33-21-11 | D13356 | | D1 | | D05110J | 49 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 38

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1104 | 286T1104 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 722 | 18 | | PA | 3-6 | 33-21-31 | D05114J | | 42 | | | | | D13372 | B1 | | | 050-099 |
| 722 | 20 | | PA | 3-6 | 33-21-31 | D13372 | | A3 | | | | | D05114J | 14 | | | 150-154, 157 |
| 722 | 20 | | PA | 2-3 | 33-21-31 | D13372 | | A3 | | | | | TB0146X | C042 | BJ | | 155-156 |
| 722 | 16 | | PA | 3-6 | 33-21-31 | D13372 | | B1 | | | | | D05114J | 29 | | | 162, 167-199 |
| 722 | 16 | | PA | 3-6 | 33-21-31 | D13372 | | B1 | | | | | D05114J | 14 | FM | | 163-165 |
| 723 | 24 | | PK | 2-5 | 33-21-31 | D00104 | | X2 | | | | | TB0174X | B020 | BJ | | 050-099, 150-199 |
| 724 | 24 | | PK | 2-6 | 33-21-31 | D10766 | | X2 | | | | | TB0174Y | C005 | BJ | | 050-099 |
| 724 | 24 | | PK | 2-6 | 33-21-31 | D10766 | | X2 | | | | | TB0146Y | C043 | BJ | | 150-199 |
| 725 | 24 | | PK | 2-3 | 33-21-31 | D13372 | | X2 | | | | | TB0174X | D020 | BJ | | 050-099, 150-199 |
| 726 | 20 | | PA | 4-1 | 33-21-31 | D05110J | | 7 | | | | | D13370 | A3 | | | 050-099 |
| 726 | 20 | | PA | 4-1 | 33-21-31 | D13370 | | A3 | | | | | D05110J | 7 | | | 150-154, 157-165, 167-199 |
| 726 | 20 | | PA | 2-7 | 33-21-31 | D13370 | | A3 | | | | | TB0146X | B042 | BJ | | 155-156, 166 |
| 727 | 20 | | PA | 2-8 | 25-42-11 | TB0146Y | | A011 | BJ | | | | D05114J | 43 | | | 050-099, 150-199 |
| 727 | 20 | | PA | 2-8 | 25-42-11 | TB0146Y | | A011 | BJ | | | | D05114J | 14 | | | 275-299 |
| 728 | 20 | | PA | 2-10 | 33-21-11 | D00092 | | B1 | | | | | TB0146Y | C028 | BJ | | 150-199 |
| 729 | 24 | | PK | 3-3 | 33-21-11 | D13356 | | Y1 | | | | | TB0174Z | 28 | BJ | | 050-099, 150-199 |
| 730 | 20 | | PA | 4-4 | 33-21-11 | D13356 | | D2 | | | | | GD0001 | A.. | 2 | | 050-099, 150-199 |
| 731 | 24 | | PK | 3-3 | 33-21-11 | D13356 | | X1 | | | | | TB0174Z | 28 | BJ | | 050-099, 150-199 |
| 732 | 20 | | PA | 1-2 | 33-21-11 | D00094 | | X2 | | | | | D13356 | A2 | | | 050-099, 150-199 |
| 735 | 22 | | PA | 3-3 | 33-22-41 | D13356 | | C3 | | | | | TB0146Y | A002 | BJ | | 050-099, 150-199 |
| 736 | 22 | | PA | 2-11 | 33-22-41 | D05110J | | 51 | | | | | TB0160Y | A016 | BJ | | 050-099, 150-199 |
| 737 | 22 | | PA | 4-9 | 33-22-41 | D05110J | | 52 | | | | | D13356 | C1 | | | 050-099, 150-199 |
| 738 | 22 | | PA | 3-3 | 33-22-41 | D13356 | | C2 | | | | | TB0160Y | C016 | BJ | | 050-099 |
| 738 | 22 | | PA | 3-3 | 33-22-41 | TB0160Y | | C016 | BJ | | | | D13356 | C2 | | | 150-199 |
| 769 | 20 | | PA | 2-8 | 33-24-11 | D05114J | | 37 | | | | | TB0174Z | 36 | BJ | | 050-099 |
| 769 | 20 | | PA | 2-8 | 33-24-11 | D05114J | | 37 | | | | | TB0174Z | 37 | BJ | | 275-299 |
| 770 | 20 | | PA | 2-8 | 33-24-11 | D05114J | | 38 | | | | | TB0174Z | 38 | BJ | | 050-099 |
| 770 | 20 | | PA | 2-8 | 33-24-11 | D05114J | | 38 | | | | | TB0146Z | 19 | BJ | | 275-299 |
| 771 | 24 | | PK | 2-11 | 33-21-12 | D05110J | | 1 | | | | | TB0174Y | A014 | BJ | | 050-099, 150-199 |
| 776 | 24 | | PK | 2-10 | 33-21-12 | D05808J | | 6 | | | | | TB0174Y | A011 | BJ | | 050-099 |
| 776 | 24 | | PK | 2-10 | 33-21-12 | TB0174Y | | A011 | BJ | | | | D05808J | 6 | | | 150-199 |
| 777 | 24 | | PK | 2-10 | 33-21-12 | D05808J | | 7 | | | | | TB0174Y | C011 | BJ | | 050-099 |
| 777 | 24 | | PK | 2-10 | 33-21-12 | TB0174Y | | C011 | BJ | | | | D05808J | 7 | | | 150-154, 162-165 |
| 777 | 20 | | PQ | 2-8 | 33-21-31 | TB0146X | | C042 | BJ | | | | D05114J | 14 | | | 155-156 |
| 777Z | | | | 0-0 | 33-21-31 | TB0146X | | DED | | | | | D05114J | DED | | | 155-156 |
| 778 | 24 | | PK | 2-10 | 33-21-12 | D05808J | | 8 | | | | | TB0174Y | C025 | BJ | | 050-099 |
| 778 | 24 | | PK | 2-10 | 33-21-12 | TB0174Y | | C025 | BJ | | | | D05808J | 8 | | | 150-199 |
| 780 | 20 | | PA | 2-8 | 35-21-12 | D05114J | | 30 | | | | | TB0160H | 29 | 2 | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 39

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1104 | 286T1104 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 783 | 20 | | PA | | 2-10 | 33-27-11 | D05134J | 32 | | | D02894 | A1 | | | 050-099 |
| 783 | 20 | | PA | | 2-10 | 33-27-11 | D02894 | A1 | | | D05134J | 32 | | | 162-199 |
| 784 | 20 | | PA | | 2-10 | 33-27-11 | TB0146Z | 33 | BJ | | D02894 | A2 | | | 050-099 |
| 785 | 20 | | PA | | 3-6 | 33-27-11 | D05134J | 33 | | | D02892 | A1 | | | 050-099 |
| 785 | 20 | | PA | | 3-6 | 33-27-11 | D02892 | A1 | | | D05134J | 33 | | | 162-199 |
| 786 | 20 | | PA | | 3-6 | 33-27-11 | TB0146Z | 33 | BJ | | D02892 | A2 | | | 050-099 |
| 787 | 20 | | PA | | 2-11 | 33-26-21 | D05110J | 19 | | | TB0146Z | 35 | BJ | | 050-099 |
| 788 | 20 | | PA | | 2-11 | 33-26-21 | D05110J | 57 | | | TB0160Y | C017 | BJ | | 050-099 |
| 790 | 20 | | PA | | 1-7 | 33-26-21 | D05110J | 16 | | | D05114J | 6 | | | 050-099 |
| 792 | 20 | | PA | | 1-7 | 33-26-21 | D05110J | 15 | | | D05114J | 7 | | | 050-099 |
| 793 | 20 | | PA | | 2-8 | 33-26-21 | TB0146X | A009 | BJ | | D05114J | 8 | | | 050-099 |
| 794 | 20 | | PA | | 2-8 | 33-26-21 | TB0160Y | C017 | BJ | | D05114J | 30 | | | 050-099 |
| 795 | 20 | | PA | | 2-8 | 26-13-11 | D05114J | 26 | | | TB0174X | B031 | BJ | | 050-099 |
| 796 | 20 | | PA | | 2-8 | 26-13-11 | D05114J | 25 | | | TB0174X | C031 | BJ | | 050-099 |
| 797 | 20 | | PA | | 2-8 | 26-13-11 | D05114J | 27 | | | TB0174Z | 42 | BJ | | 050-099 |
| 798 | 20 | | PA | | 2-8 | 26-13-11 | D05114J | 28 | | | TB0174Z | 43 | BJ | | 050-099 |
| 799 | 20 | | PA | | 2-8 | 26-13-11 | D05114J | 29 | | | TB0174Z | 41 | BJ | | 050-099 |
| 800 | 24 | | PK | | 2-8 | 33-21-31 | D05114J | 40 | | | TB0174Y | C005 | BJ | | 050-099 |
| 800 | 24 | | PK | | 2-8 | 33-21-31 | D05114J | 7 | | | TB0146Y | C043 | BJ | | 150-154, 157, 167-199 |
| 800 | 20 | | PA | | 2-5 | 33-21-31 | D00106 | A1 | | | TB0146X | A048 | BJ | | 155-156, 166 |
| 800 | 24 | | PK | | 2-8 | 33-21-31 | TB0146Y | C043 | BJ | | D05114J | 7 | | | 162-165 |
| 801 | 18 | | PA | | 5-0 | 33-21-31 | D13372 | B2 | | | T00183 | LV | E | * | 050-099 |
| 801 | 16 | | PA | | 5-0 | 33-21-31 | T00183 | LV | E | | D13372 | B2 | | | 162 |
| 801 | 16 | | PA | | 5-0 | 33-21-31 | T00183 | LV | E | * | D13372 | B2 | | | 163-165 |
| 801 | 16 | | PA | | 5-0 | 33-21-31 | D13372 | B2 | | | T00183 | LV | E | * | 166-199 |
| 802 | 20 | | PA | | 2-8 | 33-21-31 | D05114J | 15 | | | TB0174Y | A012 | BJ | | 050-099 |
| 802 | 16 | | PQ | Q2 | 2-8 | 33-21-31 | D05114J | 28 | | | TB0160F | A023 | 2 | | 155-156 |
| 802Z | | | | Q2 | 0-0 | 33-21-31 | TB0160F | DED | | | D05114J | DED | | | 155-156 |
| 803 | 20 | | PA | | 2-6 | 33-21-31 | D10766 | C1 | | | TB0146X | B048 | BJ | | 155-156, 166 |
| 804 | 20 | | PA | | 2-5 | 33-21-31 | D00104 | B1 | | | TB0146X | C048 | BJ | | 155-156, 166 |
| 805 | 20 | | PA | | 2-6 | 33-21-31 | D10766 | D1 | | | TB0146X | D048 | BJ | | 155-156, 166 |
| 806 | 20 | | PA | | 2-11 | 33-21-31 | TB0174Z | 9 | BJ | | D05110J | 11 | | | 050-099, 150-154, 157-165 |
| 806 | 20 | | PA | | 2-5 | 33-21-31 | D00104 | D1 | | | TB0146X | A049 | BJ | | 155-156, 166 |
| 806 | 20 | | PA | | 2-11 | 33-21-31 | D05110J | 11 | | | TB0174Z | 9 | BJ | | 167-199 |
| 809 | 20 | | PA | | 2-11 | 33-21-31 | D05110J | 11 | | | TB0174Z | 9 | BJ | | 155-156 |
| 815 | 20 | | PA | | 2-11 | 33-26-11 | D05110J | 41 | | | TB0146Y | A006 | BJ | | 050-099 |
| 816 | 20 | | PA | | 2-11 | 33-26-11 | D05110J | 42 | | | TB0146Z | 35 | BJ | | 050-099 |
| 822 | 20 | | PQ | S2 | 2-8 | 33-21-31 | TB0146X | D042 | BJ | | D05114J | 17 | | | 166 |

WIRE LIST

D280T132

91-21-11
Section W1100
Page 40
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1104 | 286T1104 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | |
| 822Z | | | S2 | 0-0 | 33-21-31 | TB0146X | DED | | | | D05114J | DED | | | 166 | |
| 823 | 20 | PQ | S3 | 2-11 | 33-21-31 | TB0146X | B042 | BJ | | | D05110J | 7 | | | 155-156, 166 | |
| 823Z | | | S3 | 0-0 | 33-21-31 | TB0146X | DED | | | | D05110J | DED | | | 155-156, 166 | |
| 824 | 20 | PQ | S4 | 2-8 | 33-21-31 | TB0146X | A048 | BJ | | | D05114J | 16 | | | 155-156, 166 | |
| 824Z | | | S4 | 0-0 | 33-21-31 | TB0146X | DED | | | | D05114J | DED | | | 155-156, 166 | |
| 825 | 20 | PQ | S5 | 2-8 | 33-21-31 | TB0146X | B048 | BJ | | | D05114J | 12 | | | 155-156, 166 | |
| 825Z | | | S5 | 0-0 | 33-21-31 | TB0146X | DED | | | | D05114J | DED | | | 155-156, 166 | |
| 826 | 20 | PQ | S6 | 2-8 | 33-21-31 | TB0146X | C048 | BJ | | | D05114J | 21 | | | 155-156, 166 | |
| 826Z | | | S6 | 0-0 | 33-21-31 | TB0146X | DED | | | | D05114J | DED | | | 155-156, 166 | |
| 827 | 20 | PQ | S7 | 2-11 | 33-21-31 | TB0146X | D048 | BJ | | | D05110J | 15 | | | 155-156, 166 | |
| 827Z | | | S7 | 0-0 | 33-21-31 | TB0146X | DED | | | | D05110J | DED | | | 155-156, 166 | |
| 828 | 20 | PQ | S8 | 2-11 | 33-21-31 | TB0146X | A049 | BJ | | | D05110J | 9 | | | 155-156, 166 | |
| 828Z | | | S8 | 0-0 | 33-21-31 | TB0146X | DED | | | | D05110J | DED | | | 155-156, 166 | |
| 829 | 16 | PQ | S9 | 2-8 | 33-21-31 | TB0146F | A047 | 2 | | | D05114J | 14 | FM | | 166 | |
| 829Z | | | S9 | 0-0 | 33-21-31 | TB0146F | DED | | | | D05114J | DED | | | 166 | |
| 831 | 24 | PK | | 2-8 | 33-21-31 | TB0146Y | C043 | BJ | | | D05114J | 40 | | | 166 | |
| 832 | 20 | PA | | 0-7 | 33-21-31 | TB0146Y | A032 | BJ | | | TB0174Z | 28 | BJ | | 150-154, 162-165 | |
| 832 | 20 | PA | | 2-8 | 33-22-31 | D05114J | 32 | | | | TB0146H | 1 | 2 | | 280-299 | |
| 851 | 20 | PA | | 2-6 | 33-21-31 | D10766 | A2 | | | | TB0174Z | 9 | BJ | | 166 | |
| 873 | 22 | PA | | 2-8 | 33-26-21 | D05114J | 10 | | | | TB0146Z | 35 | BJ | | 280-299 | |
| 874 | 20 | PA | | 2-8 | 33-26-21 | D05114J | 8 | | | | TB0160Y | C017 | BJ | | 280-299 | |
| 879 | 22 | PA | | 2-8 | 33-22-21 | D05114J | 36 | | | | TB0146Y | A043 | BJ | | 280-299 | |
| W1106 | 286T1106 | | | P25 INTEGRATION | | | | | | | | | | | | |
| 107 | 22 | PA | | 2-4 | 33-25-11 | D05070J | 19 | | | | TB0148Y | C010 | BJ | | ALL | |
| 109 | 16 | PA | | 3-1 | 38-13-11 | D05954J | 4 | | | | D05070J | 23 | | | 275-299 | |
| 110 | 22 | PA | | 3-1 | 33-26-11 | D05954J | 2 | | | | D05070J | 21 | | | 275-299 | |
| 111 | 18 | PA | | 3-1 | 38-32-12 | D05954J | 3 | DK | | | D05070J | 24 | DL | | 275-276 | |
| 111 | 18 | PA | | 3-1 | 38-32-16 | D05954J | 3 | DK | | | D05070J | 24 | DL | | 277-299 | |
| 112 | 22 | PA | | 1-10 | 38-32-12 | D05070J | 25 | | | | TB0162Z | 39 | BJ | | 050-099 | |
| 112 | 22 | PA | | 1-10 | 38-32-12 | TB0162Z | 39 | BJ | | | D05070J | 25 | | | 150-156, 162-165, 275-276 | |
| 112 | 22 | PA | | 1-10 | 38-32-16 | TB0162Z | 39 | BJ | | | D05070J | 25 | | | 157, 166-199, 277-299 | |
| 113 | 22 | PA | | 1-10 | 38-32-12 | D05070J | 26 | | | | TB0162Z | 39 | BJ | | 050-099 | |
| 113 | 22 | PA | | 1-10 | 38-32-12 | TB0162Z | 39 | BJ | | | D05070J | 26 | | | 150-156, 162-165, 275-276 | |
| 113 | 22 | PA | | 1-10 | 38-32-16 | TB0162Z | 39 | BJ | | | D05070J | 26 | | | 157, 166-199, 277-299 | |
| 114 | 22 | PA | | 2-6 | SPARE | D05954J | 1 | | | | TB0162Z | 39 | BJ | | 150-154 | |
| 114 | 22 | PA | | 2-6 | 38-32-12 | D05954J | 1 | | | | TB0162Z | 39 | BJ | | 275-276 | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 41

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1106 | 286T1106 | | | P25 INTEGRATION (continued) | | | | | | | | | | | |
| 114 | 22 | | PA | | 2-6 | 38-32-16 | D05954J | | 1 | | TB0162Z | 39 | BJ | | 277-299 |
| 115 | 20 | | PA | | 1-1 | 33-26-21 | TB0148Y | | A009 | BJ | TB0148Z | 14 | BJ | | 150-199 |
| 115 | 20 | | PA | | 1-10 | 33-26-21 | D05954J | | 10 | | TB0148Z | 14 | BJ | | 275-299 |
| 116 | 20 | | PA | | 2-4 | 33-26-11 | TB0148Z | | 14 | BJ | D05070J | 34 | | | 150-199 |
| 116 | 20 | | PA | | 3-1 | 33-26-11 | D05954J | | 7 | | D05070J | 36 | | | 275-299 |
| 119 | 20 | | PA | | 3-1 | 25-42-11 | D05070J | | 27 | | D05954J | 5 | | | 275-299 |
| 132 | 20 | | PA | | 2-5 | 33-26-21 | D05070J | | 38 | | TB0148X | A007 | BJ | | 275-299 |
| 133 | 20 | | PA | | 2-4 | 33-26-21 | D05070J | | 22 | | TB0148Z | 14 | BJ | | 280-299 |
| 140 | 20 | | PA | | 2-3 | 33-24-11 | D05954J | | 12 | | TB0162Y | A030 | BJ | | 275-299 |
| 141 | 22 | | PA | | 2-5 | 33-26-11 | D05070J | | 32 | | TB0162Y | C015 | BJ | | 150-199 |
| 141 | 22 | | PA | | 1-11 | 33-26-11 | D05954J | | 9 | | TB0162Y | C015 | BJ | | 275-299 |
| 142 | 22 | | PA | | 1-11 | 33-25-11 | D05070J | | 17 | | TB0148D | A030 | 2 | | 050-099 |
| 142 | 22 | | PA | | 2-4 | 33-25-11 | D05070J | | 17 | | TB0148Y | C010 | BJ | | 150-199 |
| 142 | 22 | | PA | | 1-9 | 33-25-11 | D05954J | | 8 | | TB0148Y | C010 | BJ | | 275-299 |
| 150 | 22 | | PA | | 2-1 | 33-25-11 | D05070J | | 8 | | TB0148D | A023 | 2 | | 050-099, 150-199 |
| 151 | 22 | | PA | | 1-1 | 33-25-11 | TB0148D | | C023 | 2 | TB0148D | C026 | 2 | | 050-099, 150-199 |
| 152 | 22 | | PA | | 2-1 | 33-25-11 | TB0148D | | A024 | 2 | D05070J | 7 | | | 050-099 |
| 152 | 22 | | PA | | 2-1 | 33-25-11 | D05070J | | 7 | 2 | TB0148D | A024 | 2 | | 150-154, 156 |
| 152 | 22 | | PA | | 2-1 | 33-25-11 | D05070J | | 7 | | TB0148D | C024 | 2 | | 155, 157 |
| 152 | 22 | | PA | | 2-1 | 33-25-11 | D05070J | | 7 | | TB0148D | A024 | 2 | | 162-199 |
| 154 | 22 | | PA | | 2-1 | 33-25-11 | TB0148D | | C024 | 2 | D05070J | 9 | | | 050-099 |
| 154 | 22 | | PA | | 2-1 | 33-25-11 | D05070J | | 9 | | TB0148D | C024 | 2 | | 150-154, 156, 162-199 |
| 154 | 22 | | PA | | 2-5 | 33-25-11 | D05070J | | 9 | | TB0148X | C005 | BJ | | 155, 157 |
| 159 | 20 | | PA | | 2-4 | 33-26-21 | D05070J | | 28 | | TB0148Z | 14 | BJ | | 050-099 |
| 159 | 20 | | PA | | 2-4 | 33-26-21 | D05070J | | 28 | | TB0148Y | A009 | BJ | | 150-199 |
| 160 | 20 | | PA | | 2-5 | 33-26-21 | D05070J | | 29 | | TB0148X | C007 | BJ | | 050-099 |
| 160 | 20 | | PA | | 2-4 | 33-26-21 | D05070J | | 29 | | TB0148Y | A009 | BJ | | 150-199 |
| 161 | 22 | | PA | | 2-4 | 33-26-11 | TB0148Z | | 14 | BJ | D05070J | 33 | | | 150-199 |
| 189 | 20 | | PA | | 2-5 | 26-13-11 | D05070J | | 11 | | TB0148X | D006 | BJ | | 050-099 |
| 190 | 20 | | PA | | 2-4 | 26-13-11 | D05070J | | 12 | | TB0148Y | C009 | BJ | | 050-099 |
| 191 | 20 | | PA | | 2-4 | 26-13-11 | D05070J | | 13 | | TB0148Y | A010 | BJ | | 050-099 |
| 192 | 20 | | PA | | 1-9 | 26-13-11 | D05070J | | 14 | | TB0148Y | A037 | BJ | | 050-099 |
| 198 | 22 | | PA | | 1-2 | 33-25-11 | TB0148D | | A024 | 2 | TB0148D | A030 | 2 | | 155, 157 |
| 500 | 20 | | PA | | 2-4 | 33-26-21 | D05070J | | 15 | | TB0148Y | A009 | BJ | | 050-099 |
| 501 | 20 | | PA | | 2-4 | 33-26-21 | D05070J | | 37 | | TB0148Y | A009 | BJ | | 050-099 |
| 600 | 20 | | PA | | 2-5 | 38-32-12 | D05070J | | 24 | | TB0148X | D007 | BJ | | 050-099, 150-156, 162-165 |
| 600 | 20 | | PA | | 2-5 | 38-32-16 | D05070J | | 24 | | TB0148X | D007 | BJ | | 157, 166-199 |
| 601 | 22 | | PA | | 1-11 | 33-25-11 | D05070J | | 6 | | TB0148D | A029 | 2 | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W1100
Page 42
Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1106 | 286T1106 | | | P25 INTEGRATION (continued) | | | | | | | | | | | | |
| 602 | 22 | PA | | 2-4 | 33-25-11 | TB0148Y | A011 | BJ | | D05070J | 4 | | | 050-099 | | |
| 602 | 22 | PA | | 1-11 | 33-25-11 | D05070J | | 4 | | TB0148D | C029 | 2 | | 150-199 | | |
| 603 | 22 | PA | | 1-11 | 33-25-11 | D05070J | | 3 | | TB0148D | A030 | 2 | | 150-199 | | |
| 604 | 22 | PA | | 1-11 | 33-25-11 | D05070J | | 5 | | TB0148D | C030 | 2 | | 150-199 | | |
| 605 | 22 | PA | | 2-1 | 33-25-11 | TB0148D | C023 | 2 | | D05070J | 20 | | | 050-099 | | |
| 605 | 22 | PA | | 2-1 | 33-25-11 | D05070J | | 20 | | TB0148D | C023 | 2 | | 150-199 | | |
| W1108 | 286T1108 | | | P25 INTEGRATION | | | | | | | | | | | | |
| 001 | 16 | PA | | 3-0 | 33-21-12 | D05112J | | 19 | | T00182 | LV | E | | 050-099, 150-199 | | |
| 001 | 16 | PA | | 2-0 | 33-21-12 | D05112J | | 19 | | T00182 | LV | E | | 275-299 | | |
| 002 | 16 | PA | | 3-0 | 33-21-12 | D05112J | | 15 | | T00181 | LV | E | | 050-099, 150-199 | | |
| 002 | 16 | PA | | 2-4 | 33-21-12 | D05112J | | 15 | | T00181 | LV | E | | 275-299 | | |
| 003 | 24 | PK | | 4-0 | 33-21-12 | D06736J | | 4 | | TB0148Y | A012 | BJ | | 050-099, 150-199 | | |
| 003 | 20 | PA | | 2-10 | 33-21-12 | D05112J | | 2 | | D00132 | C1 | | | 275-299 | | |
| 004 | 20 | PA | | 4-0 | 33-21-12 | D05112J | | 10 | | D00132 | A1 | | | 150-199 | | |
| 004 | 20 | PA | | 2-11 | 33-21-12 | D05112J | | 10 | | D11082 | A1 | | | 275-278 | | |
| 004 | 20 | PA | | 3-3 | 33-21-12 | TB0148Y | A012 | BJ | | D11082 | A1 | | | 280-299 | | |
| 005 | 20 | PA | | 4-0 | 33-21-12 | T00181 | HV3 | E | * | TB0162G | 1 | 2 | | 050-099, 150-199 | | |
| 005 | 20 | PA | | 3-3 | 33-21-12 | T00181 | HV3 | E | * | TB0162G | 1 | 2 | | 275-299 | | |
| 006 | 20 | PA | | 4-0 | 33-21-12 | D00132 | | D2 | | TB0162G | 1 | 2 | | 050-099, 150-199 | | |
| 006 | 20 | PA | | 3-3 | 33-21-12 | D00132 | | D2 | | TB0162G | 1 | 2 | | 275-299 | | |
| 007 | 20 | PA | | 3-3 | 33-21-12 | D00132 | | C2 | | TB0162G | 1 | 2 | | 275-299 | | |
| 008 | 20 | PA | | 4-0 | 33-21-12 | D00132 | | B2 | | TB0162G | 1 | 2 | | 050-099, 150-199 | | |
| 008 | 20 | PA | | 3-3 | 33-21-12 | D00132 | | B2 | | TB0162G | 1 | 2 | | 275-299 | | |
| 009 | 20 | PA | | 5-0 | 33-21-12 | D00132 | | A2 | | T00181 | HV2 | E | * | 150-199 | | |
| 009 | 20 | PA | | 3-7 | 33-21-12 | D11082 | | A2 | | T00181 | HV2 | E | * | 275-299 | | |
| 010 | 24 | PK | | 4-0 | 33-21-12 | D00132 | | X1 | | TB0162Z | 17 | BJ | | 050-099, 150-199 | | |
| 010 | 24 | PK | | 2-11 | 33-21-12 | D00132 | | X1 | | TB0162Z | 17 | BJ | | 275-299 | | |
| 011 | 20 | PA | | 5-0 | 33-21-12 | D00132 | | D1 | | D05118J | 4 | | | 050-099 | | |
| 011 | 20 | PA | | 4-0 | 33-21-12 | D00132 | | D1 | | D05118J | 4 | | | 150-199 | | |
| 011 | 20 | PA | | 3-8 | 33-21-12 | D00132 | | D1 | | D05118J | 4 | | | 275-299 | | |
| 012 | 20 | PA | | 5-0 | 33-21-12 | D00132 | | B1 | | D05118J | 6 | | | 050-099 | | |
| 012 | 20 | PA | | 5-0 | 33-21-12 | D00132 | | B1 | | TB0148Y | A011 | BJ | | 150-199 | | |
| 012 | 20 | PA | | 3-2 | 33-21-12 | D00132 | | B1 | | TB0148Y | A011 | BJ | | 275-299 | | |
| 013 | 20 | PA | | 4-0 | 33-21-12 | T00182 | HV3 | E | * | TB0162G | 2 | 2 | | 050-099, 150-199 | | |
| 013 | 20 | PA | | 3-0 | 33-21-12 | T00182 | HV3 | E | * | TB0162G | 2 | 2 | | 275-299 | | |
| 014 | 16 | PA | | 2-0 | 33-21-12 | T00182 | GND | E | | GDX0001 | A.. | 2 | | 050-099, 150-199 | | |
| 014 | 16 | PA | | 1-6 | 33-21-12 | T00182 | GND | E | | GDX0001 | A.. | 2 | | 275-299 | | |
| 015 | 24 | PK | | 5-0 | 33-21-12 | D13368 | | B1 | | TB0162G | 3 | 2 | | 050-099, 150-199 | | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 43

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1108 | 286T1108 | | | P25 INTEGRATION (continued) | | | | | | | | | | | |
| 015 | 24 | | PK | | 2-6 | 33-21-12 | D05112J | | 12 | | TB0162G | | 3 | 2 | 275-299 |
| 016 | 24 | | PK | | 3-0 | 33-21-12 | D05112J | | 14 | | TB0162Z | | 17 | BJ | 050-099, 150-199 |
| 016 | 24 | | PK | | 2-2 | 33-21-12 | D05112J | | 14 | | TB0162Z | | 17 | BJ | 275-299 |
| 017 | 24 | | PK | | 2-5 | 33-21-12 | D05112J | | 11 | | TB0162G | | 7 | 2 | 275-299 |
| 018 | 20 | | PA | | 4-0 | 33-21-12 | TB0162G | | 2 | 2 | D00130 | | D2 | | 050-099, 150-199 |
| 018 | 20 | | PA | | 3-3 | 33-21-12 | TB0162G | | 2 | 2 | D00130 | | D2 | | 275-299 |
| 019 | 20 | | PA | | 3-3 | 33-21-12 | TB0162G | | 2 | 2 | D00130 | | C2 | | 275-299 |
| 020 | 20 | | PA | | 4-0 | 33-21-12 | TB0162G | | 2 | 2 | D00130 | | B2 | | 050-099, 150-199 |
| 020 | 20 | | PA | | 3-3 | 33-21-12 | TB0162G | | 2 | 2 | D00130 | | B2 | | 275-299 |
| 021 | 20 | | PA | | 5-0 | 33-21-12 | T00182 | | HV2 | E | D00130 | | A2 | | 150-199 |
| 021 | 20 | | PA | | 3-3 | 33-21-12 | T00182 | | HV2 | E | D11084 | | A2 | | 275-299 |
| 022 | 24 | | PK | | 4-0 | 33-21-12 | TB0162Z | | 17 | BJ | D00130 | | X1 | | 050-099, 150-199 |
| 022 | 24 | | PK | | 2-11 | 33-21-12 | TB0162Z | | 17 | BJ | D00130 | | X1 | | 275-299 |
| 023 | 24 | | PK | | 4-0 | 33-21-12 | TB0162G | | 7 | 2 | D13368 | | X2 | | 050-099 |
| 023 | 24 | | PK | | 5-0 | 33-21-12 | TB0162G | | 7 | 2 | D13368 | | X2 | | 150-199 |
| 023 | 24 | | PK | | 3-1 | 33-21-12 | TB0162G | | 7 | 2 | D00130 | | X2 | | 275-299 |
| 024 | 20 | | PA | | 5-0 | 33-21-12 | D05916J | | 1 | | D00130 | | D1 | | 050-099, 150-199 |
| 024 | 20 | | PA | | 3-7 | 33-21-12 | D05916J | | 1 | | D00130 | | D1 | | 275-299 |
| 026 | 20 | | PA | | 5-0 | 33-21-12 | D00130 | | B1 | | D05916J | | 2 | | 050-099 |
| 026 | 20 | | PA | | 5-0 | 33-21-12 | D00130 | | B1 | | TB0148Y | | C011 | BJ | 150-199 |
| 026 | 20 | | PA | | 3-2 | 33-21-12 | D00130 | | B1 | | TB0148Y | | C011 | BJ | 275-299 |
| 027 | 20 | | PA | | 3-0 | 33-21-12 | D05916J | | 5 | | TB0148Y | | C011 | BJ | 150-199 |
| 027 | 20 | | PA | | 1-9 | 33-21-12 | D05916J | | 5 | | TB0148Y | | C011 | BJ | 275-299 |
| 028 | 20 | | PA | | 2-8 | 33-21-12 | D05914J | | 3 | | D00130 | | C1 | | 275-299 |
| 029 | 20 | | PA | | 3-0 | 33-21-12 | D05914J | | 4 | | D00130 | | A1 | | 150-199 |
| 029 | 20 | | PA | | 2-8 | 33-21-12 | D05914J | | 4 | | D11084 | | A1 | | 275-278 |
| 029 | 20 | | PA | | 3-2 | 33-21-12 | TB0148Y | | C012 | BJ | D11084 | | A1 | | 280-299 |
| 030 | 24 | | PK | | 3-3 | 33-21-12 | D00132 | | X2 | | TB0162G | | 3 | 2 | 275-299 |
| 031 | 16 | | PA | | 2-0 | 33-21-12 | T00181 | | GND | E | GDX0001 | | A.. | 2 | 050-099 |
| 031 | 16 | | PA | | 3-0 | 33-21-12 | T00181 | | GND | E | GDX0001 | | A.. | 2 | 150-199 |
| 031 | 16 | | PA | | 1-9 | 33-21-12 | T00181 | | GND | E | GDX0001 | | A.. | 2 | 275-299 |
| 032 | 20 | | PA | | 3-0 | 33-21-12 | TB0148Y | | A011 | BJ | D05118J | | 6 | | 150-199 |
| 032 | 20 | | PA | | 1-10 | 33-21-12 | TB0148Y | | A011 | BJ | D05118J | | 6 | | 275-299 |
| 033 | 20 | | PA | | 3-0 | 33-21-12 | TB0148Y | | A011 | BJ | D05118J | | 5 | | 150-199 |
| 033 | 20 | | PA | | 1-10 | 33-21-12 | TB0148Y | | A011 | BJ | D05118J | | 5 | | 275-299 |
| 034 | 22 | | PA | | 4-0 | 33-21-34 | D05112J | | 4 | | D05118J | | 9 | | 050-099 |
| 034 | 20 | | PA | | 4-0 | 33-21-34 | D05112J | | 4 | | D05118J | | 9 | | 150-154, 157-165, 167-199 |
| 034 | 20 | | PQ | BI | 4-0 | 33-21-34 | D05112J | | 4 | | D05118J | | 9 | | 155-156, 166 |

WIRE LIST
D280T132

91-21-11
Section W1100
Page 44
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1108 | 286T1108 | | | P25 INTEGRATION (continued) | | | | | | | | | | | | |
| 034 | 20 | | PA | | 3-0 | 33-21-34 | D05112J | | 4 | | | | D05118J | 9 | | 275-299 |
| 034Z | | | | BI | 0-0 | 33-21-34 | D05112J | | DED | | | | D05118J | DED | | 155-156, 166 |
| 035 | 18 | | PA | | 4-0 | 33-21-34 | D05112J | | 5 | | | | D05118J | 3 | | 050-099 |
| 035 | 16 | | PA | | 4-0 | 33-21-34 | D05112J | | 23 | | | | D05118J | 3 | | 150-199 |
| 035 | 16 | | PA | | 3-0 | 33-21-34 | D05112J | | 23 | | | | D05118J | 10 | | 275-299 |
| 037 | 22 | | PA | | 4-0 | 33-21-35 | D05116J | | 7 | | | | D05120J | 2 | | 050-099 |
| 037 | 20 | | PA | | 4-0 | 33-21-35 | D05116J | | 7 | | | | D05120J | 2 | | 150-154, 157-165, 167-199 |
| 037 | 20 | | PQ | BL | 4-0 | 33-21-35 | D05116J | | 7 | | | | D05120J | 2 | | 155-156, 166 |
| 037 | 20 | | PA | | 2-9 | 33-21-35 | D05116J | | 7 | | | | D05120J | 2 | | 275-299 |
| 037Z | | | | BL | 0-0 | 33-21-35 | D05116J | | DED | | | | D05120J | DED | | 155-156, 166 |
| 038 | 20 | | PA | | 4-0 | 33-24-11 | D05116J | | 10 | | | | D05096J | 10 | | 050-099, 150-199 |
| 038 | 20 | | PA | | 1-9 | 33-24-11 | D05116J | | 10 | | | | TB0162Y | A030 | BJ | 275-299 |
| 039 | 22 | | PA | | 3-0 | 33-25-11 | TB0148D | | A024 | 2 | | | D05116J | 16 | | 050-099 |
| 039 | 22 | | PA | | 3-0 | 33-25-11 | TB0148Y | | C010 | BJ | | | D05116J | 14 | | 150-199 |
| 039 | 22 | | PA | | 1-11 | 33-25-11 | TB0148Y | | C010 | BJ | | | D05096J | 7 | | 275-299 |
| 040 | 20 | | PA | | 4-0 | 33-26-11 | D05112J | | 6 | | | | D05096J | 19 | | 050-099 |
| 042 | 22 | | PA | | 4-0 | 33-26-11 | D05116J | | 2 | | | | D05096J | 3 | | 050-099 |
| 042 | 22 | | PA | | 3-0 | 33-26-11 | D05116J | | 2 | | | | D05096J | 3 | | 275-299 |
| 043 | 20 | | PA | | 4-0 | 33-26-11 | D05112J | | 3 | | | | D05096J | 4 | | 050-099 |
| 043 | 22 | | PA | | 3-0 | 33-26-11 | D06742J | | 15 | | | | TB0162Y | C015 | BJ | 150-199 |
| 043 | 20 | | PA | | 2-3 | 33-26-11 | D05112J | | 3 | | | | TB0162Y | C015 | BJ | 275-299 |
| 044 | 20 | | PA | | 3-0 | 33-26-21 | TB0148Z | | 14 | BJ | | | D05116J | 21 | | 050-099, 150-199 |
| 044 | 20 | | PA | | 2-0 | 33-26-21 | TB0148Z | | 14 | BJ | | | D05096J | 1 | | 275-299 |
| 048 | 16 | | PA | | 4-0 | 38-13-11 | D05116J | | 11 | FL | | | D05096J | 21 | | 050-099 |
| 048 | 16 | | PA | | 4-0 | 38-13-11 | D05116J | | 23 | | | | D05096J | 11 | FM | 150-199 |
| 048 | 16 | | PA | | 3-0 | 38-13-11 | D05116J | | 11 | | | | D05096J | 11 | | 275-299 |
| 049 | 20 | | PA | | 2-3 | 33-24-11 | D05096J | | 10 | | | | TB0162Y | A030 | BJ | 275-299 |
| 050 | 22 | | PA | | 2-1 | 33-22-42 | D05914J | | 1 | | | | TB0162Y | C019 | BJ | 275-299 |
| 051 | 22 | | PA | | 1-11 | 33-22-42 | D05914J | | 2 | | | | TB0162X | A023 | BJ | 275-299 |
| 052 | 22 | | PA | | 3-0 | 33-22-42 | D05120J | | 4 | | | | TB0162Y | C016 | BJ | 050-099 |
| 052 | 20 | | PA | | 3-0 | 33-22-42 | D05120J | | 4 | | | | TB0162Y | C016 | BJ | 150-199 |
| 052 | 22 | | PA | | 1-10 | 33-22-42 | D05120J | | 4 | | | | TB0162X | C023 | BJ | 275-299 |
| 053 | 22 | | PA | | 3-0 | 33-22-42 | D05120J | | 7 | | | | TB0162X | B023 | BJ | 050-099 |
| 053 | 22 | | PA | | 3-0 | 33-22-42 | D05120J | | 6 | | | | TB0162Y | C012 | BJ | 150-199 |
| 053 | 22 | | PA | | 1-7 | 33-22-42 | D05120J | | 5 | | | | TB0162Y | C012 | BJ | 275-299 |
| 054 | 22 | | PA | | 2-4 | 33-22-42 | D05120J | | 8 | | | | TB0162Z | 40 | BJ | 275-299 |
| 056 | 22 | | PA | | 3-0 | 33-22-42 | D05120J | | 6 | | | | TB0162X | D023 | BJ | 050-099 |
| 058 | 22 | | PA | | 1-10 | 33-26-11 | D05096J | | 4 | | | | TB0162Y | C015 | BJ | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 45

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|---------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1108 | 286T1108 | | | P25 INTEGRATION (continued) | | | | | | | | | | | |
| 059 | 20 | | PA | | 4-0 33-21-34 | D05112J | | 21 | | | D05118J | | 1 | | 150-154, 157-165, 167-199 |
| 059 | 20 | | PQ | CI | 4-0 33-21-34 | D05112J | | 21 | | | D05118J | | 1 | | 155-156, 166 |
| 059 | 20 | | PA | | 3-0 33-21-34 | D05112J | | 21 | | | D05118J | | 1 | | 275-299 |
| 059Z | | | | CI | 0-0 33-21-34 | D05112J | | DED | | | D05118J | | DED | | 155-156, 166 |
| 060 | 20 | | PA | | 3-0 33-27-11 | D05116J | | 4 | | | TB0162Y | A016 | BJ | | 050-099, 150-199 |
| 060 | 20 | | PA | | 2-2 33-27-11 | D05116J | | 4 | | | TB0162Y | A016 | BJ | | 275-299 |
| 061 | 20 | | PA | | 3-0 33-27-11 | D05120J | | 9 | | | TB0162X | A026 | BJ | | 050-099, 150-199 |
| 061 | 20 | | PA | | 2-0 33-27-11 | D05120J | | 9 | | | TB0162X | A026 | BJ | | 275-299 |
| 062 | 22 | | PA | | 3-0 33-27-11 | D05120J | | 10 | | | TB0162X | B026 | BJ | | 050-099, 150-199 |
| 062 | 22 | | PA | | 2-0 33-27-11 | D05120J | | 10 | | | TB0162X | B026 | BJ | | 275-299 |
| 063 | 22 | | PA | | 3-0 33-27-11 | D05118J | | 8 | | | TB0162X | D026 | BJ | | 050-099, 150-199 |
| 063 | 22 | | PA | | 1-7 33-27-11 | D05118J | | 8 | | | TB0162G | | 4 2 | | 275-299 |
| 064 | 20 | | PA | | 3-0 33-27-11 | D05118J | | 11 | | | TB0162X | C026 | BJ | | 050-099, 150-199 |
| 064 | 20 | | PA | | 2-1 33-27-11 | D05118J | | 11 | | | TB0162X | C026 | BJ | | 275-299 |
| 065 | 22 | | PA | | 4-0 38-32-13 | D05116J | | 5 | | | D05096J | | 12 | | 050-099 |
| 066 | 18 | | PA | | 4-0 38-32-13 | D05116J | | 6 | DL | | D05096J | | 13 | DK | 050-099 |
| 066 | 20 | | PA | | 3-0 38-32-13 | TB0148Y | | C033 | BJ | | D05096J | | 13 | | 150-156, 162-165 |
| 066 | 20 | | PA | | 3-0 38-32-16 | TB0148Y | | C033 | BJ | | D05096J | | 13 | | 157, 166-199 |
| 066 | 20 | | PA | | 2-6 38-32-13 | TB0148Y | | C033 | BJ | | D05096J | | 13 | | 275-276 |
| 066 | 20 | | PA | | 2-6 38-32-16 | TB0148Y | | C033 | BJ | | D05096J | | 13 | | 277-299 |
| 068 | 20 | | PA | | 4-0 33-26-11 | D05096J | | 5 | | | TB0148Z | | 14 | BJ | 050-099 |
| 068 | 20 | | PA | | 3-0 33-26-11 | D05116J | | 33 | | | TB0148Z | | 14 | BJ | 150-199 |
| 068 | 20 | | PA | | 2-0 33-26-11 | D05096J | | 5 | | | TB0148Z | | 14 | BJ | 275-299 |
| 071 | 24 | | PK | | 4-0 33-21-12 | D13368 | | Y2 | | | TB0148Y | A012 | BJ | | 050-099 |
| 071 | 24 | | PK | | 5-0 33-21-12 | TB0148Y | | A012 | BJ | | D13368 | | Y2 | | 150-199 |
| 073 | 20 | | PA | | 2-4 33-21-12 | D05914J | | 4 | | | TB0148Y | C012 | BJ | | 280-299 |
| 075 | 20 | | PA | | 3-0 33-21-12 | D05916J | | 2 | | | TB0148Y | C011 | BJ | | 150-199 |
| 075 | 20 | | PA | | 1-9 33-21-12 | D05916J | | 2 | | | TB0148Y | C011 | BJ | | 275-299 |
| 083 | 24 | | PK | | 3-0 33-21-12 | D13364 | | A2 | | | D11084 | | X2 | | 050-099 |
| 083 | 24 | | PK | | 3-0 33-21-12 | D11084 | | X2 | | | D13364 | | A2 | | 150-199 |
| 083 | 24 | | PK | | 2-10 33-21-12 | D11084 | | X2 | | | D05112J | | 22 | | 275-299 |
| 085 | 22 | | PA | | 3-0 21-66-31 | D06742J | | 8 | | | TB0148Y | A034 | BJ | | 050-099 |
| 085 | 22 | | PA | | 2-6 21-66-31 | TB0148Y | | A034 | BJ | | D06742J | | 8 | | 150, 152-157 |
| 085 | 22 | | PA | | 3-0 21-66-31 | TB0148Y | | A034 | BJ | | D06742J | | 8 | | 162-199 |
| 086 | 24 | | PK | | 5-0 33-21-12 | D13364 | | Y2 | | | TB0148X | A008 | BJ | | 150-199 |
| 089 | 20 | | PA | | 4-0 33-21-12 | D11084 | | B2 | | | T00182 | HV3 | E | * | 050-099 |
| 089 | 20 | | PA | | 3-9 33-21-12 | D11084 | | B2 | | | T00182 | HV3 | E | * | 150-199 |
| 089 | 20 | | PA | | 3-4 33-21-12 | D11084 | | B2 | | | T00182 | HV3 | E | * | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 46

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1108 | 286T1108 | | | P25 INTEGRATION (continued) | | | | | | | | | | | | | |
| 090 | 20 | | PA | | 4-0 | 33-21-12 | D11084 | | B1 | | | | D05914J | 3 | | | 050-099, 150-199 |
| 090 | 20 | | PA | | 2-8 | 33-21-12 | D11084 | | B1 | | | | D05914J | 10 | | | 275-299 |
| 091 | 20 | | PA | | 4-0 | 33-21-35 | D05116J | | 19 | | | | D05120J | 1 | | | 150-154, 157-165, 167-199 |
| 091 | 20 | | PQ | DP | 4-0 | 33-21-35 | D05116J | | 19 | | | | D05120J | 1 | | | 155-156, 166 |
| 091 | 20 | | PA | | 2-9 | 33-21-35 | D05116J | | 19 | | | | D05120J | 1 | | | 275-299 |
| 091Z | | | | DP | 0-0 | 33-21-35 | D05116J | | DED | | | | D05120J | DED | | | 155-156, 166 |
| 093 | 24 | | PK | | 4-0 | 33-21-12 | D11084 | | X1 | | | | TB0162Z | 17 | BJ | | 050-099, 150-199 |
| 093 | 24 | | PK | | 2-10 | 33-21-12 | D11084 | | X1 | | | | TB0162Z | 17 | BJ | | 275-299 |
| 095 | 22 | | PA | | 3-0 | 33-51-11 | D05112J | | 7 | | | | TB0162X | A025 | BJ | | 050-099, 150-199 |
| 095 | 22 | | PA | | 2-0 | 33-51-11 | D05112J | | 7 | | | | TB0162X | A025 | BJ | | 275-299 |
| 108 | 20 | | PA | | 4-0 | 33-26-11 | D05112J | | 9 | | | | D05096J | 11 | | | 050-099 |
| 115 | 20 | | PA | | 2-6 | 33-26-21 | TB0148X | | A007 | BJ | | | D05116J | 15 | | | 275-299 |
| 116 | 22 | | PA | | 3-0 | 33-25-11 | TB0148Y | | C010 | BJ | | | D05116J | 17 | | | 050-099 |
| 116 | 22 | | PA | | 4-0 | 33-25-11 | D05116J | | 17 | | | | TB0148Y | C010 | BJ | | 150-199 |
| 119 | 20 | | PA | | 3-0 | 38-32-13 | TB0148Y | | C033 | BJ | | | D05116J | 6 | | | 150-156, 162-165 |
| 119 | 20 | | PA | | 3-0 | 38-32-16 | TB0148Y | | C033 | BJ | | | D05116J | 6 | | | 157, 166-199 |
| 119 | 20 | | PA | | 1-10 | 38-32-13 | TB0148Y | | C033 | BJ | | | D05116J | 6 | | | 275-276 |
| 119 | 20 | | PA | | 1-10 | 38-32-16 | TB0148Y | | C033 | BJ | | | D05116J | 6 | | | 277-299 |
| 121 | 20 | | PA | | 1-10 | 38-32-13 | TB0148Y | | C033 | BJ | | | D05116J | 8 | | | 275-276 |
| 121 | 20 | | PA | | 1-10 | 38-32-16 | TB0148Y | | C033 | BJ | | | D05116J | 8 | | | 277-299 |
| 129 | 22 | | PA | | 3-0 | 38-32-13 | TB0148Y | | A033 | BJ | | | D05116J | 5 | | | 150-156, 162-165 |
| 129 | 22 | | PA | | 3-0 | 38-32-16 | TB0148Y | | A033 | BJ | | | D05116J | 5 | | | 157, 166-199 |
| 129 | 22 | | PA | | 1-10 | 38-32-13 | TB0148Y | | A033 | BJ | | | D05116J | 5 | | | 275-276 |
| 129 | 22 | | PA | | 1-10 | 38-32-16 | TB0148Y | | A033 | BJ | | | D05116J | 5 | | | 277-299 |
| 131 | 22 | | PA | | 1-10 | 38-32-13 | TB0148Y | | A033 | BJ | | | D05116J | 18 | | | 275-276 |
| 131 | 22 | | PA | | 1-10 | 38-32-16 | TB0148Y | | A033 | BJ | | | D05116J | 18 | | | 277-299 |
| 135 | 22 | | PA | | 3-0 | 38-32-13 | TB0148Y | | A033 | BJ | | | D05096J | 12 | | | 150-156, 162-165 |
| 135 | 22 | | PA | | 3-0 | 38-32-16 | TB0148Y | | A033 | BJ | | | D05096J | 12 | | | 157, 166-199 |
| 135 | 22 | | PA | | 2-6 | 38-32-13 | TB0148Y | | A033 | BJ | | | D05096J | 12 | | | 275-276 |
| 135 | 22 | | PA | | 2-6 | 38-32-16 | TB0148Y | | A033 | BJ | | | D05096J | 12 | | | 277-299 |
| 137 | 20 | | PA | | 4-0 | 33-21-12 | D11082 | | B1 | | | | D05112J | 2 | | | 050-099, 150-199 |
| 137 | 20 | | PA | | 2-11 | 33-21-12 | D11082 | | B1 | | | | D05112J | 20 | | | 275-299 |
| 138 | 20 | | PA | | 5-0 | 33-21-12 | D11082 | | B2 | | | | T00181 | HV3 | E | * | 050-099 |
| 138 | 20 | | PA | | 3-7 | 33-21-12 | D11082 | | B2 | | | | T00181 | HV3 | E | * | 150-199 |
| 138 | 20 | | PA | | 3-8 | 33-21-12 | D11082 | | B2 | | | | T00181 | HV3 | E | * | 275-299 |
| 139 | 24 | | PK | | 3-0 | 33-21-12 | D11082 | | X2 | | | | D13364 | B2 | | | 050-099, 150-199 |
| 139 | 24 | | PK | | 2-11 | 33-21-12 | D11082 | | X2 | | | | D05112J | 13 | | | 275-299 |
| 140 | 24 | | PK | | 4-0 | 33-21-12 | D11082 | | X1 | | | | TB0162Z | 17 | BJ | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 47

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1108 | 286T1108 | | | P25 INTEGRATION (continued) | | | | | | | | | | | | | |
| 140 | 24 | | PK | | 2-11 | 33-21-12 | D11082 | | X1 | | | | TB0162Z | 17 | BJ | | 275-299 |
| 150 | 20 | | PA | | 4-0 | 38-32-12 | D06742J | | 1 | | | | TB0162Z | 39 | BJ | | 050-099, 150-156, 162-165 |
| 150 | 20 | | PA | | 4-0 | 38-32-16 | D06742J | | 1 | | | | TB0162Z | 39 | BJ | | 157, 166-199 |
| 151 | 24 | | PK | | 4-0 | 33-21-12 | D13364 | | D3 | | | | D06736J | 12 | | | 050-099, 150-199 |
| 152 | 24 | | PK | | 4-0 | 33-21-12 | D13364 | | D1 | | | | D06736J | 1 | | | 050-099, 150-199 |
| 153 | 24 | | PK | | 4-0 | 33-21-12 | D13364 | | X2 | | | | D06736J | 2 | | | 050-099, 150-199 |
| 154 | 20 | | PA | | 4-0 | 33-21-12 | D13364 | | D2 | | | | GD0001 | A.. | 2 | | 050-099 |
| 154 | 20 | | PA | | 5-0 | 33-21-12 | D13364 | | D2 | | | | GD0001 | A.. | 2 | | 150-199 |
| 159 | 18 | | PA | | 3-0 | 33-27-11 | TB0162G | | 8 | 2 | | | D05118J | 7 | | | 150-199 |
| 173 | 22 | | PA | | 3-0 | 33-25-11 | D05116J | | 20 | | | | TB0148X | C005 | BJ | | 155, 157 |
| 184 | 22 | | PA | | 5-0 | 33-21-21 | D13368 | | C3 | | | | TB0148X | A006 | BJ | | 050-099, 150-199 |
| 185 | 24 | | PK | | 5-0 | 33-21-21 | D13368 | | C1 | | | | TB0148X | B006 | BJ | | 050-099, 150-199 |
| 187 | 24 | | PK | | 5-0 | 33-21-21 | D13368 | | C2 | | | | TB0148X | C006 | BJ | | 050-099, 150-199 |
| 188 | 24 | | PK | | 4-0 | 33-21-12 | D06736J | | 8 | | | | D13368 | A3 | | | 050-099 |
| 188 | 24 | | PK | | 4-0 | 33-21-12 | D13368 | | A3 | | | | D06736J | 8 | | | 150-199 |
| 189 | 24 | | PK | | 4-0 | 33-21-12 | D13368 | | A1 | | | | TB0162X | D022 | BJ | | 050-099 |
| 189 | 24 | | PK | | 5-0 | 33-21-12 | D13368 | | A1 | | | | TB0148X | D008 | BJ | | 150-199 |
| 190 | 24 | | PK | | 4-0 | 33-21-12 | D06736J | | 7 | | | | D13368 | B3 | | | 050-099 |
| 190 | 24 | | PK | | 4-0 | 33-21-12 | D13368 | | B3 | | | | D06736J | 7 | | | 150-199 |
| 192 | 24 | | PK | | 4-0 | 33-21-12 | D13368 | | D3 | | | | D06736J | 3 | | | 050-099, 150-199 |
| 193 | 24 | | PK | | 5-0 | 33-21-12 | D13368 | | D1 | | | | TB0148X | C008 | BJ | | 050-099, 150-199 |
| 194 | 20 | | PA | | 4-0 | 33-21-12 | D13368 | | D2 | | | | GD0001 | A.. | 2 | | 050-099 |
| 194 | 20 | | PA | | 5-0 | 33-21-12 | D13368 | | D2 | | | | GD0001 | A.. | 2 | | 150-199 |
| 195 | 24 | | PK | | 5-0 | 33-21-12 | D13364 | | Y2 | | | | TB0148X | A008 | BJ | | 050-099 |
| 196 | 24 | | PK | | 4-0 | 33-21-12 | D13364 | | A3 | | | | D06736J | 11 | | | 050-099, 150-199 |
| 197 | 24 | | PK | | 4-0 | 33-21-12 | D13364 | | A1 | | | | D06736J | 6 | | | 050-099, 150-199 |
| 198 | 24 | | PK | | 4-0 | 33-21-12 | D13364 | | B3 | | | | D06736J | 13 | | | 050-099, 150-199 |
| 199 | 24 | | PK | | 4-0 | 33-21-12 | D13364 | | B1 | | | | D06736J | 5 | | | 050-099, 150-199 |
| 201B | 22 | | PB | A | 3-0 | 23-31-14 | TB0162F | | C021 | 2 | | | D05096J | 9 | | | 050-099, 150-199 |
| 201B | 22 | | PB | A | 2-1 | 23-31-14 | TB0162F | | C021 | 2 | | | D05096J | 9 | | | 275-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-14 | TB0162F | | A021 | 2 | | | D05096J | 8 | | | ALL |
| 503 | 22 | | PA | | 1-5 | 33-27-11 | D05120J | | 7 | | | | TB0162G | 4 | 2 | | 275-299 |
| 508 | 20 | | PA | | 3-0 | 33-21-31 | TB0162Y | | C030 | BJ | | | D05112J | 17 | | | 162-199 |
| 512 | 20 | | PA | | 3-0 | 33-26-21 | D05116J | | 9 | | | | TB0148Y | A009 | BJ | | 050-099 |
| 514 | 20 | | PA | | 3-0 | 33-26-21 | D05116J | | 28 | | | | TB0148Z | 14 | BJ | | 050-099 |
| 517 | 20 | | PA | | 3-0 | 33-26-21 | D05116J | | 29 | | | | TB0148Z | 14 | BJ | | 050-099 |
| 518 | 20 | | PA | | 3-0 | 33-26-21 | D05116J | | 22 | | | | TB0148X | C007 | BJ | | 050-099 |
| 519 | 20 | | PA | | 3-0 | 33-26-21 | D05096J | | 2 | | | | TB0148Z | 14 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 48

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1108 | 286T1108 | | | P25 INTEGRATION (continued) | | | | | | | | | | | | |
| 519 | 20 | | PA | 3-0 | 33-26-21 | TB0148Z | 14 | BJ | | D05096J | 2 | | | | 162-199 | |
| 520 | 20 | | PA | 3-0 | 26-13-11 | D06742J | 24 | | | TB0148Y | A037 | BJ | | | 050-099 | |
| 521 | 20 | | PA | 3-0 | 26-13-11 | D06742J | 16 | | | TB0148X | D006 | BJ | | | 050-099 | |
| 522 | 20 | | PA | 3-0 | 26-13-11 | D06742J | 19 | | | TB0148Y | C009 | BJ | | | 050-099 | |
| 523 | 20 | | PA | 3-0 | 26-13-11 | D06742J | 20 | | | TB0148Y | A010 | BJ | | | 050-099 | |
| 531 | 20 | | PA | 4-0 | 33-21-31 | TB0162Y | C030 | BJ | | D12218 | A2 | | | | 162-199 | |
| 532 | 20 | | PA | 4-0 | 33-21-31 | TB0162Y | C030 | BJ | | D12220 | A2 | | | | 162-199 | |
| 533 | 22 | | PA | 3-0 | 21-66-31 | D06742J | 9 | | | TB0162G | 4 | 2 | | | 050-099 | |
| 533 | 22 | | PA | 2-7 | 21-66-31 | TB0162G | 4 | 2 | | D06742J | 9 | | | | 150, 152-157 | |
| 533 | 22 | | PA | 2-0 | 21-66-31 | TB0162G | 4 | 2 | | D06742J | 9 | | | | 162-199 | |
| 534 | 22 | | PA | 3-0 | 21-66-41 | D06742J | 11 | | | TB0162G | 6 | 2 | | | 050-099 | |
| 534 | 22 | | PA | 2-7 | 21-66-41 | TB0162G | 6 | 2 | | D06742J | 11 | | | | 150, 152-157 | |
| 534 | 22 | | PA | 2-0 | 21-66-41 | TB0162G | 6 | 2 | | D06742J | 11 | | | | 162-199 | |
| 535 | 22 | | PA | 3-0 | 21-66-41 | D06742J | 10 | | | TB0162G | 5 | 2 | | | 050-099 | |
| 535 | 22 | | PA | 2-7 | 21-66-41 | TB0162G | 5 | 2 | | D06742J | 10 | | | | 150, 152-157 | |
| 535 | 22 | | PA | 2-0 | 21-66-41 | TB0162G | 5 | 2 | | D06742J | 10 | | | | 162-199 | |
| 600 | 20 | | PA | 5-0 | 33-21-12 | D11082 | A2 | | | T00181 | HV2 | E | | | 050-099 | |
| 600 | 20 | | PA | 3-7 | 33-21-12 | D11082 | A2 | | | T00181 | HV2 | E | * | | 150-199 | |
| 601 | 20 | | PA | 3-0 | 38-32-12 | D06742J | 7 | | | TB0148X | D007 | BJ | | | 050-099, 150-156, 162-165 | |
| 601 | 20 | | PA | 3-0 | 38-32-16 | D06742J | 7 | | | TB0148X | D007 | BJ | | | 157, 166-199 | |
| 602 | 20 | | PA | 2-6 | 33-21-12 | D05112J | 10 | | | TB0148Y | A012 | BJ | | | 280-299 | |
| 604 | 20 | | PA | 4-0 | 25-42-11 | D05116J | 12 | | | D05096J | 14 | | | | 050-099 | |
| 604 | 16 | | PA | 4-0 | 25-42-11 | D05096J | 14 | FM | | D05116J | 11 | FL | | | 150-199 | |
| 604 | 20 | | PA | 3-0 | 25-42-11 | D05096J | 14 | | | D05116J | 12 | | | | 275-299 | |
| 605 | 18 | | PA | 4-0 | 26-13-11 | D05116J | 25 | DL | | D06742J | 2 | DL | | | 050-099 | |
| 605 | 18 | | PA | 4-0 | 26-13-11 | D05116J | 25 | DL | | D06742J | 2 | DK | | | 150-199 | |
| 606 | 20 | | PA | 4-0 | 26-13-11 | D05116J | 26 | | | D06742J | 29 | | | | 050-099, 150-199 | |
| 607 | 20 | | PA | 4-0 | 26-13-11 | D05116J | 27 | | | D06742J | 18 | | | | 050-099 | |
| 607 | 20 | | PA | 4-0 | 26-13-11 | D05116J | 27 | | | D06742J | 16 | | | | 150-199 | |
| 608 | 20 | | PA | 4-0 | 26-13-11 | D05116J | 28 | | | D06742J | 17 | | | | 150-199 | |
| 609 | 20 | | PA | 4-0 | 26-13-11 | D05116J | 29 | | | D06742J | 18 | | | | 150-199 | |
| 610 | 20 | | PA | 3-0 | 26-13-11 | D05116J | 30 | | | TB0148Y | C009 | BJ | | | 050-099 | |
| 610 | 20 | | PA | 4-0 | 26-13-11 | D05116J | 30 | | | D06742J | 19 | | | | 150-199 | |
| 611 | 20 | | PA | 3-0 | 26-13-11 | D05116J | 31 | | | TB0148Y | A010 | BJ | | | 050-099 | |
| 611 | 20 | | PA | 4-0 | 26-13-11 | D05116J | 31 | | | D06742J | 20 | | | | 150-199 | |
| 612 | 20 | | PA | 3-0 | 26-13-11 | D05116J | 32 | | | TB0148Y | A037 | BJ | | | 050-099 | |
| 612 | 20 | | PA | 4-0 | 26-13-11 | D05116J | 32 | | | D06742J | 24 | | | | 150-199 | |
| 613 | 22 | | PA | 4-0 | 33-26-11 | D05116J | 2 | | | D06742J | 3 | | | | 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 49

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|------------------------------------|-------|-------------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1108 | 286T1108 | P25 INTEGRATION (continued) | | | | | | | | | | | | | |
| 614 | 22 | PA | | 4-0 | 33-26-11 | D05116J | | 3 | | | D06742J | 4 | | | 150-199 |
| 615 | 22 | PA | | 4-0 | 33-26-11 | D05116J | | 9 | | | D06742J | 5 | | | 150-199 |
| 617 | 22 | PA | | 3-0 | 33-26-11 | TB0148Z | | 14 | BJ | | D06742J | 6 | | | 150-199 |
| 618 | 22 | PA | | 4-0 | 33-26-11 | D05112J | | 3 | BJ | | D06742J | 31 | | | 150-199 |
| 620 | 20 | PA | | 3-0 | 33-26-21 | D05116J | | 22 | | | TB0148Y | A009 | BJ | | 150-199 |
| 621 | 22 | PA | | 3-0 | 33-25-11 | D05116J | | 13 | | | TB0148D | A026 | 2 | | 050-099, 150-199 |
| 622 | 24 | PK | | 4-0 | 33-21-12 | D13368 | | Y1 | | | TB0148Z | 27 | BJ | | 050-099, 150-199 |
| 623 | 24 | PK | | 4-0 | 33-21-12 | D13368 | | X1 | | | TB0148Z | 27 | BJ | | 050-099, 150-199 |
| 624 | 24 | PK | | 4-0 | 33-21-12 | D13364 | | Y1 | | | TB0148Z | 27 | BJ | | 050-099, 150-199 |
| 626 | 24 | PK | | 4-0 | 33-21-12 | D13364 | | X1 | | | TB0148Z | 27 | BJ | | 050-099, 150-199 |
| 627 | 20 | PA | | 5-0 | 33-21-12 | D11084 | | A2 | | | T00182 | HV2 | E | | 050-099 |
| 627 | 20 | PA | | 3-9 | 33-21-12 | D11084 | | A2 | | | T00182 | HV2 | E | * | 150-199 |
| 628 | 24 | PK | | 3-0 | 33-21-12 | D00130 | | X2 | | | D13368 | A2 | | | 050-099 |
| 628 | 24 | PK | | 3-0 | 33-21-12 | D13368 | | A2 | | | D00130 | X2 | | | 150-199 |
| 629 | 24 | PK | | 3-0 | 33-21-12 | D00132 | | X2 | | | D13368 | B2 | | | 050-099 |
| 629 | 24 | PK | | 3-0 | 33-21-12 | D13368 | | B2 | | | D00132 | X2 | | | 150-199 |
| 630 | 20 | PA | | 4-0 | 33-21-12 | D11082 | | A1 | | | D05112J | 10 | | | 050-099 |
| 630 | 20 | PA | | 4-0 | 33-21-12 | D11082 | | A1 | | | D05112J | 27 | | | 150-199 |
| 630 | 20 | PA | | 2-6 | 33-21-12 | D05112J | | 27 | | | TB0148Y | A012 | BJ | | 280-299 |
| 631 | 20 | PA | | 4-0 | 33-21-12 | D11084 | | A1 | | | D05914J | 4 | | | 050-099 |
| 631 | 20 | PA | | 4-0 | 33-21-12 | D11084 | | A1 | | | D05914J | 8 | | | 150-199 |
| 631 | 20 | PA | | 2-4 | 33-21-12 | D05914J | | 8 | | | TB0148Y | C012 | BJ | | 280-299 |
| 632 | 22 | PA | | 4-0 | 33-22-42 | D06736J | | 9 | | | TB0148X | A005 | BJ | | 050-099 |
| 632 | 22 | PA | | 4-0 | 33-22-42 | TB0148X | | A005 | BJ | | D06736J | 9 | | | 150-199 |
| 633 | 22 | PA | | 4-0 | 33-22-42 | D06736J | | 10 | | | TB0148X | B005 | BJ | | 050-099 |
| 633 | 22 | PA | | 4-0 | 33-22-42 | TB0148X | | B005 | BJ | | D06736J | 10 | | | 150-199 |
| 646 | 22 | PA | | 3-0 | 33-22-42 | D05120J | | 7 | | | TB0148Z | 17 | BJ | | 150, 152-199 |
| 646 | 22 | PA | | 3-0 | 33-22-42 | D05120J | | 7 | | | TB0162Z | 38 | BJ | | 151 |
| 647 | 18 | PA | | 3-0 | 33-27-11 | TB0148G | | 40 | 2 | | D05120J | 16 | DK | | 150-199 |
| 648 | 20 | PA | | 3-6 | 33-21-12 | D00132 | | A2 | | | T00181 | HV2 | E | * | 275-299 |
| 649 | 20 | PA | | 3-8 | 33-21-12 | D05118J | | 2 | | | D00132 | A1 | | | 275-299 |
| 650 | 20 | PA | | 3-3 | 33-21-12 | D00130 | | A2 | | | T00182 | HV2 | E | * | 275-299 |
| 651 | 20 | PA | | 3-7 | 33-21-12 | D05916J | | 3 | | | D00130 | A1 | | | 275-299 |
| 656 | 20 | PA | | 4-0 | 33-21-31 | D12218 | | A2 | | | TB0162Y | C028 | BJ | | 050-099 |
| 657 | 24 | PK | | 4-0 | 33-21-31 | D12218 | | X1 | | | TB0162H | 32 | 2 | | 050-099 |
| 657 | 24 | PK | | 4-0 | 33-21-31 | TB0162H | | 32 | 2 | | D12218 | X1 | | | 162-199 |
| 658 | 24 | PK | | 5-0 | 33-21-31 | D12218 | | X2 | | | D05096J | 37 | | | 050-099 |
| 658 | 24 | PK | | 5-0 | 33-21-31 | D05096J | | 37 | | | D12218 | X2 | | | 162-199 |
| 659 | 20 | PA | | 5-0 | 33-21-31 | D12218 | | A1 | | | D05118J | 10 | | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 50

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------|----|------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1108 | 286T1108 | | | P25 INTEGRATION (continued) | | | | | | | | | | | | |
| 660 | 24 | | PK | | 4-0 | 33-21-31 | D05116J | | 14 | | D05096J | | 38 | | 050-099 | |
| 660 | 24 | | PK | | 4-0 | 33-21-31 | D05096J | | 38 | | D05116J | | 34 | | 162-199 | |
| 661 | 20 | | PA | | 4-0 | 33-21-31 | D12220 | | A2 | | TB0162Y | C028 | BJ | | 050-099 | |
| 662 | 24 | | PK | | 4-0 | 33-21-31 | D12220 | | X1 | | TB0162H | 32 | 2 | | 050-099 | |
| 662 | 24 | | PK | | 4-0 | 33-21-31 | TB0162H | | 32 | 2 | D12220 | | X1 | | 162-199 | |
| 663 | 24 | | PK | | 5-0 | 33-21-31 | D12220 | | X2 | | D05096J | | 39 | | 050-099 | |
| 663 | 24 | | PK | | 5-0 | 33-21-31 | D05096J | | 39 | | D12220 | | X2 | | 162-199 | |
| 664 | 20 | | PA | | 5-0 | 33-21-31 | D12220 | | A1 | | D05118J | | 12 | | 050-099, 162-199 | |
| 666 | 22 | | PA | | 3-0 | 33-25-11 | D05116J | | 18 | | TB0148D | A029 | 2 | | 050-099 | |
| 667 | 22 | | PA | | 3-0 | 33-25-11 | TB0148D | | C029 | 2 | D05096J | | 34 | | 050-099 | |
| 668 | 22 | | PA | | 2-0 | 33-25-11 | TB0148D | | C029 | 2 | TB0148D | C030 | 2 | | 050-099 | |
| 669 | 22 | | PA | | 4-0 | 33-25-11 | TB0148D | | A029 | 2 | D05096J | | 26 | | 050-099 | |
| 670 | 22 | | PA | | 3-0 | 33-25-11 | TB0148Y | | A011 | BJ | D05116J | | 20 | | 050-099 | |
| 671 | 22 | | PA | | 3-0 | 33-25-11 | TB0148Y | | A011 | BJ | D05096J | | 6 | | 050-099 | |
| 672 | 22 | | PA | | 3-0 | 33-25-11 | TB0148Y | | C010 | BJ | D05096J | | 7 | | 050-099 | |
| 673 | 22 | | PA | | 4-0 | 33-25-11 | TB0148D | | A030 | 2 | D05096J | | 28 | | 050-099 | |
| 674 | 20 | | PA | | 3-0 | 33-21-31 | D05112J | | 17 | | TB0162Y | C028 | BJ | | 050-099 | |
| 826 | 20 | | PA | | 4-0 | 33-26-11 | D05112J | | 16 | | D05096J | | 18 | | 050-099 | |
| W1109 | 286T1109 | | | ATTENDANT CALL LIGHT-RIGHT | | | | | | | | | | | | |
| 001 | 22 | | PA | | 5-0 | 23-42-11 | D06051P | | 1 | | L01116 | =P | \$ | | 050-099, 150-199 | |
| 002 | 22 | | PA | | 5-0 | 23-34-13 | D06051P | | 2 | | L00732 | =P | \$ | | 050-099, 150-199 | |
| 003 | 22 | | PA | | 5-0 | 33-25-11 | D06051P | | 3 | | L00689 | =P | \$ | | 050-099, 150-199 | |
| 004 | 20 | | PA | | 5-0 | 23-42-11 | D06051P | | 4 | | L01116 | =G | \$ | | 050-099, 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W1100

Page 51 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1110 | 286T1110 | | | P19 INTEGRATION | | | | | | | | | | | |
| 001 | 24 | | PK | | 1-8 | 35-21-11 | D05710J | | | | TB0160H | 39 | 2 | | ALL |
| 002 | 24 | | PK | | 2-2 | 35-21-11 | D05710J | | | | TB0160H | 19 | 2 | | ALL |
| 003 | 22 | | PA | | 2-2 | 35-21-11 | D05710J | | | 6 | TB0160G | 18 | 2 | | ALL |
| 004 | 24 | | PK | | 2-6 | 35-21-11 | D00136 | | D2 | | TB0160H | 39 | 2 | | ALL |
| 005 | 24 | | PK | | 2-6 | 35-21-11 | D00136 | | X1 | | TB0160H | 39 | 2 | | ALL |
| 006 | 22 | | PA | | 2-1 | 35-21-11 | D00136 | | X2 | | D00134 | 1 | | | ALL |
| 007 | 24 | | PK | | 2-10 | 35-21-11 | D00136 | | D1 | | TB0160G | 26 | 2 | | ALL |
| 008 | 24 | | PK | | 2-10 | 35-21-11 | D00138 | | D1 | | TB0160G | 24 | 2 | | ALL |
| 009 | 24 | | PK | | 2-11 | 35-21-11 | D00138 | | X1 | | TB0160H | 19 | 2 | | ALL |
| 010 | 24 | | PK | | 2-11 | 35-21-11 | D00138 | | D2 | | TB0160H | 19 | 2 | | ALL |
| 011 | 24 | | PK | | 3-5 | 35-21-11 | D00134 | | 7 | | TB0160H | 39 | 2 | | ALL |
| 013 | 20 | | PA | | 4-6 | 35-21-11 | D00134 | | 6 | | GDX0002 | D.. | 2 | | 050-099 |
| 013 | 20 | | PA | | 4-7 | 35-21-11 | D00134 | | 6 | | GDX0002 | D.. | 2 | | 150-199, 275-299 |
| 014 | 20 | | PA | | 4-6 | 35-21-11 | D00134 | | 2 | | GDX0002 | D.. | 2 | | 050-099 |
| 014 | 20 | | PA | | 4-7 | 35-21-11 | D00134 | | 2 | | GDX0002 | D.. | 2 | | 150-199, 275-299 |
| 015 | 24 | | PK | | 3-10 | 35-21-11 | D00134 | | 5 | | TB0160G | 22 | 2 | | ALL |
| 016 | 24 | | PK | | 3-10 | 35-21-11 | D00134 | | 3 | | TB0160G | 22 | 2 | | ALL |
| 017 | 24 | | PK | | 2-1 | 35-21-11 | D05710J | | 5 | | TB0160G | 22 | 2 | | ALL |
| 018 | 24 | | PK | | 2-6 | 35-21-11 | D05710J | | 8 | | TB0160G | 7 | 2 | | ALL |
| 019 | 24 | | PK | | 4-2 | 35-21-11 | D00140 | | 2 | | TB0160G | 7 | 2 | | ALL |
| 020 | 24 | | PK | | 1-11 | 35-21-11 | D00140 | | 5 | | D00138 | X2 | | | 050-099 |
| 020 | 24 | | PK | | 2-0 | 35-21-11 | D00140 | | 5 | | D00138 | X2 | | | 150-199, 275-299 |
| 021 | 24 | | PK | | 4-0 | 35-21-11 | D00140 | | 7 | | TB0160H | 19 | 2 | | 050-099 |
| 021 | 24 | | PK | | 3-11 | 35-21-11 | D00140 | | 7 | | TB0160H | 19 | 2 | | 150-199, 275-299 |
| 022 | 24 | | PK | | 4-2 | 35-21-11 | D00140 | | 3 | | TB0160G | 7 | 2 | | ALL |
| 023 | 22 | | PA | | 2-9 | 35-21-11 | D00144 | | B2 | | TB0160G | 18 | 2 | | ALL |
| 024 | 24 | | PK | | 2-9 | 35-21-11 | D00144 | | A2 | | TB0160H | 19 | 2 | | ALL |
| 025 | 24 | | PK | | 2-8 | 35-21-11 | D00144 | | A1 | | TB0160G | 24 | 2 | | ALL |
| 026 | 24 | | PK | | 2-8 | 35-21-11 | D00144 | | X1 | | TB0160G | 24 | 2 | | ALL |
| 027 | 20 | | PA | | 3-5 | 35-21-11 | D00144 | | B1 | | GDX0001 | D.. | 2 | | ALL |
| 028 | 20 | | PA | | 3-5 | 35-21-11 | D00144 | | X2 | | GDX0001 | D.. | 2 | | ALL |
| 029 | 20 | | PA | | 3-5 | 35-21-11 | D00142 | | A1 | | GDX0002 | D.. | 2 | | ALL |
| 030 | 20 | | PA | | 3-5 | 35-21-11 | D00142 | | X2 | | GDX0002 | D.. | 2 | | ALL |
| 031 | 22 | | PA | | 2-10 | 35-21-11 | D00142 | | A2 | | TB0160G | 18 | 2 | | ALL |
| 032 | 24 | | PK | | 3-3 | 35-21-11 | D00142 | | B2 | | TB0160H | 39 | 2 | | 050-099 |
| 032 | 24 | | PK | | 2-3 | 35-21-11 | D00142 | | B2 | | TB0160H | 39 | 2 | | 150-199, 275-299 |
| 033 | 24 | | PK | | 2-7 | 35-21-11 | D00142 | | B1 | | TB0160G | 26 | 2 | | ALL |
| 034 | 24 | | PK | | 2-7 | 35-21-11 | D00142 | | X1 | | TB0160G | 26 | 2 | | ALL |
| 037 | 16 | | PA | | 2-0 | 35-21-12 | D05710J | | 14 | | TB0160G | 28 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W1110
 Page 1
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1110 | 286T1110 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | |
| 038 | 16 | | PA | 2-10 | 35-21-12 | D00136 | | A2 | | | | | TB0160G | 28 | 2 | | 050-099 |
| 038 | 16 | | PA | 2-9 | 35-21-12 | D00136 | | A2 | | | | | TB0160G | 28 | 2 | | 150-199, 275-299 |
| 039 | 16 | | PA | 2-8 | 35-21-12 | D00136 | | A1 | | | | | TB0160H | 29 | 2 | | ALL |
| 040 | 16 | | PA | 2-7 | 35-21-12 | D00138 | | A1 | | | | | TB0160H | 29 | 2 | | 050-099 |
| 040 | 16 | | PA | 2-8 | 35-21-12 | D00138 | | A1 | | | | | TB0160H | 29 | 2 | | 150-199, 275-299 |
| 041 | 16 | | PA | 2-9 | 35-21-12 | D00138 | | A2 | | | | | TB0160G | 28 | 2 | | ALL |
| 042 | 16 | | PA | 2-6 | 35-21-12 | D05750J | | 3 | | | | | TB0160H | 29 | 2 | | 050-099 |
| 042 | 16 | | PA | 2-7 | 35-21-12 | D05740J | | 1 | | | | | TB0160H | 29 | 2 | | 150-199, 275-299 |
| 043 | 16 | | PA | 2-7 | 35-21-12 | D05740J | | 2 | | | | | TB0160H | 29 | 2 | | ALL |
| 044 | 20 | | PA | 2-0 | 35-21-12 | D05448J | | 1 | | | | | TB0160H | 29 | 2 | | 050-099 |
| 044 | 20 | | PA | 2-1 | 35-21-12 | D05448J | | 1 | | | | | TB0160H | 29 | 2 | | 150-199, 275-299 |
| 045 | 16 | | PA | 1-10 | 35-21-13 | D05710J | | 16 | | | | | TB0160G | 31 | 2 | | 050-099 |
| 045 | 16 | | PA | 1-11 | 35-21-13 | D05710J | | 16 | | | | | TB0160G | 31 | 2 | | 150-199, 275-299 |
| 046 | 16 | | PA | 2-9 | 35-21-13 | D00136 | | C2 | | | | | TB0160G | 31 | 2 | | ALL |
| 047 | 16 | | PA | 2-9 | 35-21-13 | D00136 | | C1 | | | | | TB0160H | 32 | 2 | | 050-099 |
| 047 | 16 | | PA | 2-8 | 35-21-13 | D00136 | | C1 | | | | | TB0160H | 32 | 2 | | 150-199, 275-299 |
| 048 | 16 | | PA | 2-8 | 35-21-13 | D00138 | | C2 | | | | | TB0160G | 31 | 2 | | 050-099 |
| 048 | 16 | | PA | 2-7 | 35-21-13 | D00138 | | C2 | | | | | TB0160G | 31 | 2 | | 150-199, 275-299 |
| 049 | 16 | | PA | 2-8 | 35-21-13 | D00138 | | C1 | | | | | TB0160H | 32 | 2 | | 050-099 |
| 049 | 16 | | PA | 2-7 | 35-21-13 | D00138 | | C1 | | | | | TB0160H | 32 | 2 | | 150-199, 275-299 |
| 050 | 20 | | PA | 2-1 | 35-21-13 | D05448J | | 2 | | | | | TB0160H | 32 | 2 | | 050-099 |
| 050 | 20 | | PA | 2-1 | 35-21-13 | TB0160H | | 32 | 2 | | | | D05448J | 2 | | | 150-199 |
| 051 | 16 | | PA | 2-6 | 35-21-13 | D05750J | | 4 | | | | | TB0160H | 32 | 2 | | 050-099 |
| 051 | 16 | | PA | 2-4 | 35-21-13 | D05746J | | 1 | | | | | TB0160H | 32 | 2 | | 150-199, 275-299 |
| 052 | 16 | | PA | 2-5 | 35-21-13 | D05746J | | 2 | | | | | TB0160H | 32 | 2 | | 050-099 |
| 052 | 16 | | PA | 2-4 | 35-21-13 | D05746J | | 2 | | | | | TB0160H | 32 | 2 | | 150-199, 275-299 |
| 053 | 16 | | PA | 1-9 | 35-21-14 | D05710J | | 18 | | | | | TB0160G | 34 | 2 | | ALL |
| 054 | 16 | | PA | 2-7 | 35-21-14 | D00136 | | B2 | | | | | TB0160G | 34 | 2 | | ALL |
| 055 | 16 | | PA | 2-7 | 35-21-14 | D00136 | | B1 | | | | | TB0160H | 35 | 2 | | ALL |
| 056 | 16 | | PA | 2-6 | 35-21-14 | D00138 | | B2 | | | | | TB0160G | 34 | 2 | | ALL |
| 057 | 16 | | PA | 2-6 | 35-21-14 | D00138 | | B1 | | | | | TB0160H | 35 | 2 | | ALL |
| 058 | 20 | | PA | 1-11 | 35-21-14 | D05448J | | 3 | | | | | TB0160H | 35 | 2 | | 275-299 |
| 059 | 16 | | PA | 2-7 | 35-21-14 | D05750J | | 1 | FM | | | | TB0160H | 35 | 2 | | 050-099 |
| 059 | 16 | | PA | 2-7 | 35-21-14 | D05750J | | 1 | | | | | TB0160H | 35 | 2 | | 150-199, 275-299 |
| 060 | 16 | | PA | 2-7 | 35-21-14 | D05750J | | 2 | FM | | | | TB0160H | 35 | 2 | | 050-099 |
| 060 | 16 | | PA | 2-7 | 35-21-14 | D05750J | | 2 | | | | | TB0160H | 35 | 2 | | 150-199, 275-299 |
| 061 | 24 | | PK | 2-9 | 23-31-13 | D00144 | | C2 | | | | | TB0174G | 22 | 2 | | ALL |
| 062 | 20 | | PA | 3-5 | 23-31-13 | D00144 | | C1 | | | | | GDX0001 | D.. | 2 | | ALL |
| 063 | 24 | | PK | 3-10 | 23-31-13 | D00142 | | C2 | | | | | TB0174G | 22 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|------------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1110 | 286T1110 | | | P19 INTEGRATION (continued) | | | | | | | | | | | | | | |
| 063 | 24 | | PK | | 2-10 | 23-31-13 | D00142 | | | C2 | | | | TB0174G | 22 | 2 | | 150-199, 275-299 |
| 064 | 20 | | PA | | 3-7 | 23-31-13 | D00142 | | | C1 | | | | GDX0001 | D.. | 2 | | 050-099 |
| 064 | 20 | | PA | | 4-0 | 23-31-13 | D00142 | | | C1 | | | | GDX0001 | D.. | 2 | | 150-199, 275-299 |
| 065 | 18 | | PA | | 3-6 | 25-63-11 | D08094J | | | 4 | DL | | | D08098J | 4 | | | 050-099 |
| 065 | 18 | | PA | | 3-7 | 25-63-11 | D08094J | | | 4 | DL | | | D08098J | 4 | | | 150-199 |
| 065 | 18 | | PA | | 3-7 | 25-63-11 | D08094J | | | 4 | | | | D08098J | 4 | | | 275-299 |
| 066 | 20 | | PA | | 3-6 | 25-63-11 | D08094J | | | 1 | | | | D08098J | 1 | | | 050-099 |
| 066 | 20 | | PA | | 3-7 | 25-63-11 | D08094J | | | 1 | | | | D08098J | 1 | | | 150-199, 275-299 |
| 073 | 22 | | PA | | 2-4 | 33-51-11 | D05710J | | | 7 | | | | TB0160Y | C014 | BJ | | ALL |
| 076 | 18 | | PA | | 2-1 | 33-22-31 | TB0146G | | | 32 | 2 | | | D05448J | 4 | | | 275-278 |
| 076 | 18 | | PA | | 2-10 | 33-22-31 | TB0146H | | | 1 | 2 | | | D05448J | 4 | | | 280-299 |
| 077 | 20 | | PA | | 1-11 | 33-24-11 | D05448J | | | 6 | | | | TB0174Z | 37 | BJ | | 275-276, 280-299 |
| 077 | 20 | | PQ | DB | 1-11 | 33-24-11 | D05448J | | | 6 | | | | TB0174Z | 37 | BJ | | 277-278 |
| 077Z | | | | DB | 0-0 | 33-24-11 | D05448J | | | DED | | | | TB0174Z | DED | | | 277-278 |
| 078 | 20 | | PA | | 2-5 | 33-24-11 | D05448J | | | 7 | | | | TB0146Z | 19 | BJ | | 275-276, 280-299 |
| 078 | 20 | | PQ | DC | 2-5 | 33-24-11 | D05448J | | | 7 | | | | TB0146Z | 19 | BJ | | 277-278 |
| 078Z | | | | DC | 0-0 | 33-24-11 | D05448J | | | DED | | | | TB0146Z | DED | | | 277-278 |
| 081 | 22 | | PA | | 2-11 | 33-21-21 | D10798 | | | C1 | | | | TB0174X | A019 | BJ | | 050-099 |
| 081 | 22 | | PA | | 3-3 | 33-21-21 | D10798 | | | C1 | | | | TB0174X | A019 | BJ | | 150-199, 275-299 |
| 082 | 20 | | PA | | 3-6 | 33-21-21 | D10798 | | | C2 | | | | GDX0001 | A.. | 2 | | 050-099 |
| 082 | 20 | | PA | | 3-8 | 33-21-21 | D10798 | | | C2 | | | | GDX0001 | A.. | 2 | | 150-199, 275-299 |
| 083 | 22 | | PA | | 2-11 | 33-22-42 | D10798 | | | D1 | | | | TB0174X | B019 | BJ | | 050-099 |
| 083 | 22 | | PA | | 3-3 | 33-22-42 | D10798 | | | D1 | | | | TB0174X | B019 | BJ | | 150-199, 275-299 |
| 084 | 20 | | PA | | 3-6 | 33-22-42 | D10798 | | | D2 | | | | GDX0001 | A.. | 2 | | 050-099 |
| 084 | 20 | | PA | | 3-8 | 33-22-42 | D10798 | | | D2 | | | | GDX0001 | A.. | 2 | | 150-199, 275-299 |
| 085 | 22 | | PA | | 2-5 | 33-51-11 | D10798 | | | X1 | | | | TB0146Z | 33 | BJ | | 050-099 |
| 085 | 22 | | PA | | 2-7 | 33-51-11 | D10798 | | | X1 | | | | TB0146Z | 33 | BJ | | 150-199, 275-299 |
| 086 | 22 | | PA | | 2-7 | 33-51-11 | D10798 | | | X2 | | | | D05710J | 11 | | | 050-099 |
| 086 | 22 | | PA | | 2-10 | 33-51-11 | D10798 | | | X2 | | | | D05710J | 11 | | | 150-199, 275-299 |
| 087 | 20 | | PQ | B | 2-7 | 33-51-11 | D10798 | | | A1 | | | | D05710J | 10 | | | 050-099 |
| 087 | 20 | | PQ | B | 2-9 | 33-51-11 | D10798 | | | A1 | | | | D05710J | 10 | | | 150-199, 275-299 |
| 087Z | | | | B | 0-0 | 33-51-11 | D10798 | | | DED | | | | D05710J | DED | | | ALL |
| 088 | 20 | | PQ | C | 3-3 | 33-51-11 | D10798 | | | A2 | | | | TB0160H | 3 | 2 | | 050-099 |
| 088 | 20 | | PQ | C | 3-5 | 33-51-11 | D10798 | | | A2 | | | | TB0160H | 3 | 2 | | 150-199, 275-299 |
| 088Z | | | | C | 0-0 | 33-51-11 | D10798 | | | DED | | | | TB0160H | DED | | | ALL |
| 089 | 20 | | PQ | D | 2-11 | 33-51-11 | D10798 | | | A3 | | | | TB0174X | D019 | BJ | | 050-099 |
| 089 | 20 | | PQ | D | 3-3 | 33-51-11 | D10798 | | | A3 | | | | TB0174X | D019 | BJ | | 150-199, 275-299 |
| 089Z | | | | D | 0-0 | 33-51-11 | D10798 | | | DED | | | | TB0174X | DED | | | ALL |
| 090 | 20 | | PQ | E | 2-7 | 33-51-11 | D10798 | | | B1 | | | | D05710J | 9 | | | 050-099 |

WIRE LIST

D280T132

91-21-11
Section W1110
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------------|------|------|--------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1110 | 286T1110 | | | P19 INTEGRATION (continued) | | | | | | | | | | | |
| 090 | 20 | PQ | E | | 2-9 | 33-51-11 | D10798 | | B1 | | D05710J | | 9 | | 150-199, 275-299 |
| 090Z | | | E | | 0-0 | 33-51-11 | D10798 | | DED | | D05710J | | DED | | ALL |
| 091 | 20 | PQ | F | | 2-4 | 33-51-11 | D10798 | | B2 | | TB0146Z | | 40 | BJ | 050-099 |
| 091 | 20 | PQ | F | | 2-6 | 33-51-11 | D10798 | | B2 | | TB0146Z | | 40 | BJ | 150-199, 275-299 |
| 091Z | | | F | | 0-0 | 33-51-11 | D10798 | | DED | | TB0146Z | | DED | | ALL |
| 092 | 20 | PQ | G | | 2-11 | 33-51-11 | D10798 | | B3 | | TB0174X | | C019 | BJ | 050-099 |
| 092 | 20 | PQ | G | | 3-3 | 33-51-11 | D10798 | | B3 | | TB0174X | | C019 | BJ | 150-199, 275-299 |
| 092Z | | | G | | 0-0 | 33-51-11 | D10798 | | DED | | TB0174X | | DED | | ALL |
| W1111 | 286T1111 | | | ATTENDANT CALL LIGHT-LEFT | | | | | | | | | | | |
| 001 | 22 | PA | | | 4-0 | 23-42-11 | D06053P | | 1 | | L01115 | | =P | \$ | 050-099, 150-199 |
| 002 | 22 | PA | | | 4-0 | 23-34-13 | D06053P | | 2 | | L00731 | | =P | \$ | 050-099, 150-199 |
| 003 | 22 | PA | | | 4-0 | 33-25-11 | D06053P | | 3 | | L00690 | | =P | \$ | 050-099, 150-199 |
| 004 | 20 | PA | | | 4-0 | 23-42-11 | D06053P | | 4 | | L01115 | | =G | \$ | 050-099, 150-199 |
| W1112 | 286T1112 | | | P25 INTEGRATION | | | | | | | | | | | |
| 001 | 18 | PA | | | 3-0 | 25-63-11 | D08100J | | 4 | DL | D08102J | | 4 | DK | ALL |
| 002 | 20 | PA | | | 3-0 | 25-63-11 | D08100J | | 1 | | D08102J | | 1 | | ALL |
| 003 | 16 | PA | | | 3-0 | 35-21-12 | D05752J | | 2 | | D05736J | | 1 | | 050-099 |
| 004 | 16 | PA | | | 3-0 | 35-21-13 | D05752J | | 3 | | D05728J | | 1 | | 050-099 |
| 005 | 16 | PA | | | 3-0 | 35-21-14 | D05752J | | 1 | | D05730J | | 1 | | 050-099 |
| W1113 | 286T1113 | | | ATTENDANT CALL LIGHT-LEFT | | | | | | | | | | | |
| 001 | 22 | PA | | | 6-0 | 23-42-11 | D06057P | | 1 | | L00196 | | =P | \$ | 050-099, 150-154, 156, 162-199, 277-299 |
| 002 | 22 | PA | | | 6-0 | 23-34-13 | D06057P | | 2 | | L00581 | | =P | \$ | 050-099, 150-154, 156, 162-199 |
| 002 | 22 | PA | | | 6-0 | 23-34-13 | D06057P | | 2 | | L00687 | | =P | \$ | 277-278 |
| 002 | 22 | PA | | | 6-0 | 23-34-13 | D06057P | | 2 | | L00685 | | =P | \$ | 280-299 |
| 003 | 22 | PA | | | 6-0 | 33-25-11 | D06057P | | 3 | | L01195 | | =P | \$ | 050-099 |
| 003 | 22 | PA | | | 6-0 | 33-25-11 | D06057P | | 3 | | L01087 | | =P | \$ | 150-154, 156, 162-199 |
| 003 | 22 | PA | | | 6-0 | 33-25-11 | D06057P | | 3 | | L01161 | | =P | \$ | 277-299 |
| 004 | 20 | PA | | | 6-0 | 23-42-11 | D06057P | | 4 | | L00196 | | =G | \$ | 050-099, 150-154, 156, 162-199, 277-299 |
| W1114 | 286T1114 | | | ELECTRICAL SYSTEMS CARD FILE P50 | | | | | | | | | | | |
| 001 | 22 | PA | | | 4-0 | 28-21-12 | D01882 | | 19 | | D08036J | | 6 | | ALL |
| 002 | 22 | PA | | | 4-0 | 21-51-11 | D10062 | | 16 | | GDX0005 | | D.. | 2 | ALL |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1114 | 286T1114 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 003 | 24 | | PK | | 4-0 | 21-51-11 | D10062 | | 26 | | | | TB0158Y | A005 | BJ | | ALL |
| 004 | 24 | | PK | | 4-0 | 21-51-11 | D10062 | | 25 | | | | TB0158Y | C006 | BJ | | ALL |
| 005 | 24 | | PK | | 4-0 | 21-51-21 | D10064 | | 26 | | | | TB0158Y | C007 | BJ | | ALL |
| 006 | 24 | | PK | | 4-0 | 21-51-21 | D10064 | | 25 | | | | TB0158Y | A008 | BJ | | ALL |
| 007 | 22 | | PA | | 4-0 | 21-51-21 | D10064 | | 16 | | | | GD0005 | D.. | 2 | | ALL |
| 008 | 22 | | PA | | 4-0 | 28-21-12 | D01882 | | 3 | | | | D08036J | 5 | | | ALL |
| 009 | 22 | | PA | | 4-0 | 28-21-12 | D01882 | | 6 | | | | D08036J | 4 | | | ALL |
| 010 | 22 | | PA | | 4-0 | 28-21-12 | D01882 | | 5 | | | | GD0003 | D.. | 2 | | ALL |
| 011 | 22 | | PA | | 4-0 | 21-58-11 | D10062 | | 49 | | | | GD0004 | D.. | 2 | | ALL |
| 012 | 24 | | PK | | 4-0 | 21-58-11 | D10062 | | 56 | | | | D10064 | 56 | | | ALL |
| 013 | 22 | | PA | | 3-0 | 22-24-11 | TB0182D | | A025 | 2 | | | D04885J | 1 | | | ALL |
| 014 | 24 | | PK | | 4-0 | 22-12-31 | D02674 | | 22 | | | | D04885J | 6 | | | ALL |
| 015 | 24 | | PK | | 4-0 | 22-12-31 | D02674 | | 23 | | | | D04885J | 7 | | | ALL |
| 016 | 24 | | PK | | 4-0 | 21-58-11 | TB0248X | | A002 | BJ | | | D10064 | 49 | | | ALL |
| 017 | 22 | | PA | | 4-0 | 27-58-21 | D02674 | | 8 | | | | GD0003 | A.. | 2 | | ALL |
| 018 | 22 | | PA | | 3-0 | 36-11-51 | D10064 | | 17 | | | | GD0004 | D.. | 2 | | ALL |
| 019 | 22 | | PA | | 4-0 | 27-58-21 | D02674 | | 7 | | | | D08028J | 1 | | | ALL |
| 020 | 22 | | PQ | O | 4-0 | 28-21-12 | D01882 | | 9 | | | | D08038J | 11 | | | ALL |
| 020Z | | | | O | 0-0 | 28-21-12 | D01882 | | 8 | | | | D08038J | | | FE | ALL |
| 021 | 22 | | PQ | L | 4-0 | 28-21-12 | D01882 | | 16 | | | | D08038J | 6 | | | ALL |
| 021Z | | | | L | 0-0 | 28-21-12 | D01882 | | 17 | | | | D08038J | 5 | | | ALL |
| 022 | 24 | | PK | | 4-0 | 22-12-31 | D02674 | | 38 | | | | D04885J | 8 | | | ALL |
| 023 | 24 | | PK | | 4-0 | 22-12-31 | D02674 | | 39 | | | | D04885J | 9 | | | ALL |
| 024 | 22 | | PQ | M | 4-0 | 28-21-12 | D01882 | | 12 | | | | D08038J | 8 | | | ALL |
| 024Z | | | | M | 0-0 | 28-21-12 | D01882 | | 13 | | | | D08038J | | | FD | ALL |
| 025 | 22 | | PQ | N | 4-0 | 28-21-12 | D01882 | | 15 | | | | D08038J | 4 | | | ALL |
| 025Z | | | | N | 0-0 | 28-21-12 | D01882 | | 14 | | | | D08038J | 1 | | | ALL |
| 026 | 22 | | PA | | 4-0 | 27-58-21 | D02674 | | 43 | | | | GD0003 | D.. | 2 | | ALL |
| 027 | 24 | | PK | | 4-0 | 27-58-21 | D02674 | | 58 | | | | TB0182D | C025 | 2 | | ALL |
| 028 | 22 | | PA | | 4-0 | 36-11-51 | D10064 | | 61 | | | | TB0248X | B002 | BJ | | ALL |
| 029 | 22 | | PA | | 4-0 | 27-61-11 | TB0182D | | A020 | 2 | | | D04885J | 5 | | | ALL |
| 032 | 24 | | PK | | 4-0 | 21-51-11 | TB0182D | | C023 | 2 | | | D02674 | 24 | | | 050-099, 150-199, 275-276 277-299 |
| 032 | 24 | | PK | | 4-0 | 21-51-11 | TB0182F | | A023 | 2 | | | D02674 | 24 | | | ALL |
| 033 | 24 | | PK | | 4-0 | 21-51-11 | TB0158F | | C024 | 2 | | | D02674 | 27 | | | ALL |
| 034 | 22 | | PA | | 4-0 | 29-11-32 | D02246 | | 16 | | | | D08036J | 1 | | | ALL |
| 035 | 22 | | PA | | 4-0 | 29-11-32 | D02246 | | 13 | | | | D08036J | 7 | | | ALL |
| 036 | 22 | | PA | | 4-0 | 29-11-32 | D02246 | | 10 | | | | D08036J | 3 | | | ALL |
| 037 | 22 | | PA | | 4-0 | 29-11-32 | D02246 | | 1 | | | | GD0003 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1110
Page 5
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1114 | 286T1114 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 038 | 22 | PA | | 3-0 | 36-11-52 | D10062 | | 17 | | | | | GDX0004 | D.. | 2 | | ALL |
| 040 | 22 | PA | | 4-0 | 29-11-32 | D02246 | | 4 | | | | | D08036J | 12 | | | ALL |
| 041 | 22 | PA | | 4-0 | 29-11-32 | D02246 | | 7 | | | | | D08036J | 8 | | | ALL |
| 042 | 24 | PK | | 4-0 | 29-11-32 | D02246 | | 18 | | | | | D08036J | 11 | | | ALL |
| 043 | 24 | PV | J | 4-0 | 31-51-41 | D02674 | | 28 | | | | | TB0158Y | C008 | BJ | | 050-099 |
| 043 | 24 | PV | J | 4-0 | 31-51-41 | D02674 | | 28 | | | | | TB0248X | B001 | BJ | | 150-199 |
| 043 | 24 | PV | J | 5-0 | 31-51-41 | D02674 | | 28 | | | | | TB0248X | B001 | BJ | | 275-299 |
| 043Z | | | J | 0-0 | 31-51-41 | D02674 | | DED | | | | | TB0158Y | DED | | | 050-099 |
| 043Z | | | J | 0-0 | 31-51-41 | D02674 | | DED | | | | | TB0248X | DED | | | 150-199, 275-299 |
| 044 | 24 | PK | | 5-0 | 27-58-21 | D02674 | | 29 | | | | | TB0182D | C019 | 2 | | ALL |
| 045 | 22 | PA | | 4-0 | 29-11-32 | D02246 | | | | FA | | | GDX0003 | S.. | 2 | | ALL |
| 046 | 24 | PK | | 4-0 | 29-21-31 | D10062 | | 59 | | | | | D08036J | 18 | | | ALL |
| 047 | 24 | PK | | 3-0 | 29-21-31 | D10062 | | 30 | | | | | D10064 | 59 | | | ALL |
| 048 | 24 | PK | | 4-0 | 29-21-31 | D08036J | | 19 | | | | | D10064 | 30 | | | ALL |
| 050 | 22 | PA | | 4-0 | 28-22-12 | D10062 | | 2 | | | | | GDX0003 | D.. | 2 | | ALL |
| 051 | 24 | PK | | 4-0 | 28-22-12 | D10062 | | 37 | | | | | TB0248X | D001 | BJ | | ALL |
| 052 | 24 | PK | | 4-0 | 28-22-12 | D10064 | | 37 | | | | | D08036J | 13 | | | ALL |
| 053 | 22 | PA | | 4-0 | 28-22-12 | D10064 | | 2 | | | | | GDX0003 | D.. | 2 | | ALL |
| 055 | 22 | PA | | 4-0 | 36-11-52 | D10062 | | 61 | | | | | TB0248X | B012 | BJ | | ALL |
| 057 | 24 | PK | | 4-0 | 73-21-18 | D10064 | | 63 | | | | | TB0182Y | C014 | BJ | | 050-099, 162-199, 277-299 |
| 057 | 24 | PK | | 4-0 | 73-21-18 | D10064 | | 63 | | | | | TB0182Y | A013 | BJ | | 150-157, 275-276 |
| 058 | 24 | PK | | 4-0 | 73-21-18 | TB0182X | | A011 | BJ | | | | D10064 | 65 | | | 050-099, 275-299 |
| 058 | 24 | PK | | 4-0 | 73-21-18 | D10064 | | 65 | | | | | TB0182X | A011 | BJ | | 150-199 |
| 059 | 22 | PA | | 4-0 | 73-21-18 | D10064 | | 31 | | | | | GDX0003 | D.. | 2 | | ALL |
| 060 | 24 | PK | | 4-0 | 73-21-18 | TB0182Y | | C008 | BJ | | | | D08028J | 2 | | | 050-099 |
| 060 | 24 | PK | | 3-0 | 73-21-18 | D08028J | | 2 | | | | | TB0182Y | C008 | BJ | | 155-199 |
| 060 | 24 | PK | | 3-0 | 73-21-18 | TB0182Y | | C008 | BJ | | | | D08028J | 2 | | | 277-299 |
| 060A | 24 | PK | | 3-0 | 73-21-18 | TB0182Y | | C008 | BJ | | | | D08028J | 2 | | | 150-154 |
| 060A | 24 | PK | | 5-0 | 73-21-18 | TB0182Y | | C008 | BJ | | | | D08028J | 2 | | | 275-276 |
| 061 | 24 | PK | | 4-0 | 73-21-18 | TB0182Y | | C014 | BJ | | | | D08028J | 3 | | | 050-099 |
| 061 | 24 | PK | | 3-0 | 73-21-18 | D08028J | | 3 | | | | | TB0182Y | A013 | BJ | | 150-157 |
| 061 | 24 | PK | | 3-0 | 73-21-18 | D08028J | | 3 | | | | | TB0182Y | C014 | BJ | | 162-199 |
| 061 | 24 | PK | | 3-0 | 73-21-18 | TB0182Y | | A013 | BJ | | | | D08028J | 3 | | | 275-276 |
| 061 | 24 | PK | | 3-0 | 73-21-18 | TB0182Y | | C014 | BJ | | | | D08028J | 3 | | | 277-299 |
| 062 | 24 | PV | CL | 4-0 | 73-21-18 | D10062 | | 8 | | | | | D08036J | 16 | | | 050-099, 275-299 |
| 062 | 24 | PV | D | 4-0 | 73-21-18 | D10062 | | 8 | | | | | D08036J | 16 | | | 150-199 |
| 062Z | | | CL | 0-0 | 73-21-18 | D10062 | | DED | | | | | D08036J | DED | | | 050-099, 275-299 |
| 062Z | | | D | 0-0 | 73-21-18 | D10062 | | DED | | | | | D08036J | DED | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1114 | 286T1114 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | |
| 063 | 24 | | PV | CM | 4-0 | 73-21-18 | D10064 | | | | D08036J | | 17 | | 050-099, 275-299 |
| 063 | 24 | | PV | E | 4-0 | 73-21-18 | D10064 | | | | D08036J | | 17 | | 150-199 |
| 063Z | | | | CM | 0-0 | 73-21-18 | D10064 | | DED | | D08036J | | DED | | 050-099, 275-299 |
| 063Z | | | | E | 0-0 | 73-21-18 | D10064 | | DED | | D08036J | | DED | | 150-199 |
| 064 | 22 | | PA | | 4-0 | 73-21-18 | D10064 | | | | GDX0003 | | D.. | 2 | ALL |
| 065 | 24 | | PK | | 4-0 | 73-21-18 | D10062 | | | | TB0182Y | | C008 | BJ | 050-099, 155-199, 277-299 |
| 065A | 24 | | PK | | 4-0 | 73-21-18 | D10062 | | | | TB0182Y | | C008 | BJ | 150-154 |
| 065A | 24 | | PK | | 5-0 | 73-21-18 | D10062 | | | | TB0182Y | | C008 | BJ | 275-276 |
| 066 | 22 | | PA | | 4-0 | 73-21-18 | D10062 | | | | GDX0003 | | D.. | 2 | ALL |
| 067 | 24 | | PK | | 4-0 | 73-21-18 | D10062 | | | | TB0182X | | A012 | BJ | ALL |
| 068 | 22 | | PA | | 4-0 | 73-21-18 | D10062 | | | | GDX0003 | | D.. | 2 | ALL |
| 069 | 22 | | PA | | 4-0 | 73-21-18 | D10064 | | | | GDX0003 | | D.. | 2 | ALL |
| 070 | 24 | | PV | W | 4-0 | 80-11-11 | D10064 | | | | D08028J | | 18 | | ALL |
| 070Z | | | | W | 0-0 | 80-11-11 | D10064 | | DED | | D08028J | | DED | | ALL |
| 071 | 24 | | PV | X | 4-0 | 80-11-11 | D10064 | | | | D08028J | | 19 | | ALL |
| 071Z | | | | X | 0-0 | 80-11-11 | D10064 | | DED | | D08028J | | DED | | ALL |
| 072 | 22 | | PQ | P | 4-0 | 30-31-11 | D10062 | | | | GDX0003 | | D.. | 2 | ALL |
| 072Z | | | | P | 0-0 | 30-31-11 | D10062 | | DED | | GDX0003 | | DED | | ALL |
| 073 | 24 | | PV | Q | 4-0 | 30-31-11 | D10062 | | | | TB0248Y | | C013 | BJ | ALL |
| 073Z | | | | Q | 0-0 | 30-31-11 | D10062 | | DED | | TB0248Y | | DED | | ALL |
| 074 | 24 | | PV | R | 4-0 | 30-31-11 | D10064 | | | | TB0248Y | | C013 | BJ | ALL |
| 074Z | | | | R | 0-0 | 30-31-11 | D10064 | | DED | | TB0248Y | | DED | | ALL |
| 075 | 22 | | PQ | T | 4-0 | 30-31-11 | D10064 | | | | GDX0005 | | D.. | 2 | ALL |
| 075Z | | | | T | 0-0 | 30-31-11 | D10064 | | DED | | GDX0005 | | DED | | ALL |
| 076 | 24 | | PK | | 4-0 | 30-34-21 | D10062 | | | | TB0248X | | D002 | BJ | ALL |
| 077 | 22 | | PA | | 3-0 | 30-34-21 | D10062 | | | | GDX0005 | | D.. | 2 | 050-099 |
| 077 | 22 | | PA | | 4-0 | 30-34-21 | D10062 | | | | GDX0005 | | D.. | 2 | 150-199, 275-299 |
| 078 | 22 | | PA | | 4-0 | 30-31-21 | D10062 | | | | GDX0005 | | D.. | 2 | ALL |
| 079 | 24 | | PK | | 4-0 | 30-31-21 | D10062 | | | | TB0248Y | | A014 | BJ | ALL |
| 080 | 24 | | PK | | 4-0 | 30-31-21 | D10064 | | | | TB0248Y | | A014 | BJ | ALL |
| 081 | 22 | | PA | | 4-0 | 30-31-21 | D10064 | | | | GDX0005 | | D.. | 2 | ALL |
| 082 | 24 | | PV | DG | 4-0 | 30-34-11 | D10064 | | | | TB0248X | | C002 | BJ | 050-099, 150-199 |
| 082 | 24 | | PV | U | 4-0 | 30-34-11 | D10064 | | | | TB0248X | | C002 | BJ | 275-299 |
| 082Z | | | | DG | 0-0 | 30-34-11 | D10064 | | DED | | TB0248X | | DED | | 050-099, 150-199 |
| 082Z | | | | U | 0-0 | 30-34-11 | D10064 | | DED | | TB0248X | | DED | | 275-299 |
| 083 | 22 | | PQ | DH | 3-0 | 30-34-11 | D10064 | | | | GDX0005 | | D.. | 2 | 050-099 |
| 083 | 22 | | PQ | DH | 4-0 | 30-34-11 | D10064 | | | | GDX0005 | | D.. | 2 | 150-199 |
| 083 | 22 | | PQ | V | 4-0 | 30-34-11 | D10064 | | | | GDX0005 | | D.. | 2 | 275-299 |

WIRE LIST

D280T132

91-21-11
Section W1110
Page 7
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1114 | 286T1114 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 083Z | | | | DH | 0-0 | 30-34-11 | D10064 | | DED | | | | GDX0005 | DED | | | 050-099, 150-199 |
| 083Z | | | | V | 0-0 | 30-34-11 | D10064 | | DED | | | | GDX0005 | DED | | | 275-299 |
| 084 | 24 | PK | | | 4-0 | 80-11-21 | D10062 | | 18 | | | | D08036J | 20 | | | ALL |
| 085 | 24 | PK | | | 4-0 | 80-11-21 | D10062 | | 40 | | | | D08036J | 21 | | | ALL |
| 086 | 22 | PA | | | 4-0 | 73-21-18 | D10062 | | 31 | | | | GDX0003 | D.. | 2 | | ALL |
| 087 | 24 | PK | | | 4-0 | 24-51-52 | D10062 | | 34 | | | | TB0248X | A015 | BJ | | 050-099, 150-199 |
| 087 | 24 | PK | | | 4-0 | 24-51-52 | D10062 | | 34 | | | | TB0248Y | A009 | BJ | | 275-299 |
| 088 | 24 | PK | | | 4-0 | 24-51-52 | D10062 | | 27 | | | | TB0248X | B015 | BJ | | 050-099, 150-199 |
| 088 | 24 | PK | | | 4-0 | 24-51-52 | D10062 | | 27 | | | | TB0248Y | A010 | BJ | | 275-299 |
| 089 | 24 | PK | | | 4-0 | 24-51-52 | D10064 | | 27 | | | | TB0248X | C015 | BJ | | 050-099, 150-199 |
| 089 | 24 | PK | | | 4-0 | 24-51-52 | D10064 | | 27 | | | | TB0248Y | A010 | BJ | | 275-299 |
| 090 | 24 | PK | | | 4-0 | 24-51-52 | D10064 | | 34 | | | | TB0248X | D015 | BJ | | 050-099, 150-199 |
| 090 | 24 | PK | | | 4-0 | 24-51-52 | D10064 | | 34 | | | | TB0248Y | A009 | BJ | | 275-299 |
| 091 | 24 | PK | | | 3-0 | 73-21-15 | D08028J | | 20 | | | | TB0158G | 10 | 2 | | ALL |
| 092 | 24 | PV | DQ | | 4-0 | 73-21-11 | D10062 | | 5 | | | | TB0182X | A027 | BJ | | ALL |
| 092F | 20 | UA | | | 3-0 | 73-21-11 | D10062 | | | | FB | | GDX0004 | S.. | 2 | | 050-099, 150-199 |
| 092F | 20 | UA | | | 4-0 | 73-21-11 | D10062 | | | | FW | | GDX0004 | S.. | 2 | | 275-299 |
| 092Z | | | | DQ | 0-0 | 73-21-11 | D10062 | | | | FB | | TB0182X | B027 | BJ | | 050-099, 150-199 |
| 092Z | | | | DQ | 0-0 | 73-21-11 | D10062 | | | | FW | | TB0182X | B027 | BJ | | 275-299 |
| 093 | 24 | PV | DR | | 4-0 | 73-21-11 | D10062 | | 12 | | | | TB0182Y | C006 | BJ | | ALL |
| 093F | 20 | UA | | | 3-0 | 73-21-11 | D10062 | | | | FC | | GDX0004 | S.. | 2 | | 050-099, 150-199 |
| 093F | 20 | UA | | | 4-0 | 73-21-11 | D10062 | | | | FR | | GDX0004 | S.. | 2 | | 275-299 |
| 093Z | | | | DR | 0-0 | 73-21-11 | D10062 | | | | FC | | TB0182Y | C004 | BJ | | 050-099, 150-199 |
| 093Z | | | | DR | 0-0 | 73-21-11 | D10062 | | | | FR | | TB0182Y | C004 | BJ | | 275-299 |
| 094 | 24 | PV | DS | | 3-0 | 73-21-11 | D10064 | | 5 | | | | TB0182X | C027 | BJ | | 050-099, 150-199 |
| 094 | 24 | PV | DS | | 4-0 | 73-21-11 | D10064 | | 5 | | | | TB0182X | C027 | BJ | | 275-299 |
| 094F | 20 | UA | | | 3-0 | 73-21-11 | D10064 | | | | FF | | GDX0004 | S.. | 2 | | 050-099, 150-199 |
| 094F | 20 | UA | | | 4-0 | 73-21-11 | D10064 | | | | FS | | GDX0004 | S.. | 2 | | 275-299 |
| 094Z | | | | DS | 0-0 | 73-21-11 | TB0182X | | | D027 | BJ | | D10064 | | | FF | 050-099, 150-199 |
| 094Z | | | | DS | 0-0 | 73-21-11 | D10064 | | | | FS | | TB0182X | D027 | BJ | | 275-299 |
| 095 | 24 | PV | DT | | 4-0 | 73-21-11 | D10064 | | 12 | | | | TB0182Y | A007 | BJ | | ALL |
| 095F | 20 | UA | | | 3-0 | 73-21-11 | D10064 | | | | FF | | GDX0004 | S.. | 2 | | 050-099, 150-199 |
| 095F | 20 | UA | | | 4-0 | 73-21-11 | D10064 | | | | FV | | GDX0004 | S.. | 2 | | 275-299 |
| 095Z | | | | DT | 0-0 | 73-21-11 | TB0182Y | | | C007 | BJ | | D10064 | | | FF | 050-099, 150-199 |
| 095Z | | | | DT | 0-0 | 73-21-11 | D10064 | | | | FV | | TB0182Y | C007 | BJ | | 275-299 |
| 096 | 24 | PV | DU | | 3-0 | 73-21-11 | D08028J | | 4 | | | | TB0182Y | A007 | BJ | | ALL |
| 096Z | | | | DU | 0-0 | 73-21-11 | D08028J | | 5 | | | | TB0182Y | C007 | BJ | | ALL |
| 101 | 24 | PK | | | 4-0 | 73-21-18 | D10064 | | 6 | | | | TB0248X | A016 | BJ | | ALL |
| 102 | 22 | PA | | | 4-0 | 73-21-18 | D10064 | | 15 | | | | GDX0005 | D.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|--------|------|------|--------|-------|------|------|---------|-------------|----|---|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1114 | 286T1114 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | | |
| 105 | 22 | | PA | 3-0 | 73-21-18 | D10062 | | 15 | | | | | | GDY0005 | D.. | 2 | | ALL |
| 106 | 24 | | PK | 4-0 | 73-21-18 | D10062 | | 6 | | | | | | TB0248X | B016 | BJ | | ALL |
| 107 | 22 | | PA | 4-0 | 80-11-11 | D10064 | | 48 | | | | | | GDY0005 | D.. | 2 | | ALL |
| 108 | 22 | | PA | 4-0 | 80-11-11 | D10064 | | 39 | | | | | | GDY0005 | D.. | 2 | | ALL |
| 109 | 22 | | PA | 4-0 | 80-11-21 | D10062 | | 48 | | | | | | GDY0005 | D.. | 2 | | ALL |
| 110 | 22 | | PA | 4-0 | 80-11-21 | D10062 | | 39 | | | | | | GDY0005 | D.. | 2 | | ALL |
| 111 | 22 | | PA | 3-0 | 21-58-11 | D08036J | | 24 | | | | | | TB0158F | A011 | 2 | | ALL |
| 112 | 24 | | PK | 2-0 | 21-58-14 | D08028J | | 21 | | | | | | TB0158G | | 27 | 2 | 050-099 |
| 112 | 24 | | PK | 3-0 | 21-58-14 | D08028J | | 21 | | | | | | TB0158Y | C014 | BJ | | 150-152, 275-276 |
| 112 | 24 | | PK | 3-0 | 21-58-14 | D08028J | | 21 | | | | | | TB0158Y | C008 | BJ | | 153-199 |
| 112 | 24 | | PK | 3-0 | 21-58-14 | D08028J | | 21 | | | | | | TB0158Y | A002 | BJ | | 277-299 |
| 113 | 24 | | PK | 3-0 | 21-58-15 | D08036J | | 22 | | | | | | TB0182X | C016 | BJ | | ALL |
| 114 | 24 | | PK | 3-0 | 21-58-11 | D08036J | | 23 | | | | | | TB0158F | C011 | 2 | | ALL |
| 115 | 24 | | PK | 3-0 | 21-58-11 | D08028J | | 23 | | | | | | TB0182Y | A001 | BJ | | ALL |
| 116 | 24 | | PK | 3-0 | 21-58-11 | D08028J | | 24 | | | | | | TB0182Y | C002 | BJ | | ALL |
| 117 | 24 | | PK | 3-0 | 21-58-11 | D08028J | | 22 | | | | | | TB0158Y | C003 | BJ | | 050-099, 277-299 |
| 117 | 24 | | PK | 3-0 | 21-58-11 | D08028J | | 22 | | | | | | TB0158G | | 2 | 2 | 150-199, 275-276 |
| 119 | 24 | | PK | 3-0 | 27-58-21 | TB0182D | | C025 | 2 | | | | | TB0182D | C026 | 2 | | ALL |
| 120 | 24 | | PK | 3-0 | 27-58-21 | TB0182D | | C019 | 2 | | | | | TB0182D | C020 | 2 | | ALL |
| 121 | 24 | | PK | 4-0 | 27-51-31 | D02674 | | 52 | | | | | | TB0158F | A024 | 2 | | ALL |
| 130 | 22 | | PA | 4-0 | 73-21-18 | D10062 | | 46 | | | | | | GDY0005 | D.. | 2 | | 050-099, 150-199, 277-299 |
| 130 | 22 | | PA | 5-0 | 73-21-18 | D10062 | | 46 | | | | | | GDY0005 | D.. | 2 | | 275-276 |
| 131 | 24 | | PK | 4-0 | 73-21-18 | TB0248X | | C016 | BJ | | | | | D10062 | | 14 | | 050-099, 150-199, 277-299 |
| 131 | 24 | | PK | 5-0 | 73-21-18 | TB0248X | | C016 | BJ | | | | | D10062 | | 14 | | 275-276 |
| 132 | 24 | | PK | 4-0 | 73-21-18 | TB0248X | | D016 | BJ | | | | | D10064 | | 14 | | 050-099, 150-199, 277-299 |
| 132 | 24 | | PK | 5-0 | 73-21-18 | TB0248X | | D016 | BJ | | | | | D10064 | | 14 | | 275-276 |
| 133 | 22 | | PA | 4-0 | 73-21-18 | D10064 | | 46 | | | | | | GDY0005 | D.. | 2 | | 050-099, 150-199, 277-299 |
| 133 | 22 | | PA | 5-0 | 73-21-18 | D10064 | | 46 | | | | | | GDY0005 | D.. | 2 | | 275-276 |
| 134 | 22 | | PA | 2-0 | 28-31-12 | TB0182D | | C020 | 2 | | | | | D08028J | | 16 | | 050, 162-164 |
| 134 | 22 | | PA | 20-0 | 28-31-12 | TB0182D | | C020 | 2 | | | | | D08028J | | 16 | | 051-099 |
| 134 | 22 | | PA | 2-0 | 28-31-12 | TB0182D | | CAP | Y | | | | | D08028J | | 16 | | 155-157, 165-199, 277-299 |
| 201B | 24 | | PL | A | 4-0 | 27-51-31 | D02674 | | 18 | | | | | TB0158F | A019 | 2 | | ALL |
| 201R | 24 | | PL | A | 0-0 | 27-51-31 | D02674 | | 17 | | | | | TB0158F | C019 | 2 | | ALL |
| 202B | 22 | | PB | B | 4-0 | 27-58-21 | D02674 | | 9 | | | | | D08028J | | 9 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1110
Page 9
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1114 | 286T1114 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | | | |
| 202R | 22 | PB | B | 0-0 | 27-58-21 | D02674 | | 10 | | | | | D08028J | 10 | | | ALL |
| 205B | 22 | PB | AA | 4-0 | 27-58-21 | D02674 | | 35 | | | | | D08028J | 11 | | | ALL |
| 205R | 22 | PB | AA | 0-0 | 27-58-21 | D02674 | | 31 | | | | | D08028J | 12 | | | ALL |
| 206B | 24 | PW | I | 4-0 | 29-11-32 | D02246 | | 21 | | | | | D08036J | 10 | | | ALL |
| 206R | 24 | PW | I | 0-0 | 29-11-32 | D02246 | | 20 | | | | | D08036J | 9 | | | ALL |
| 206Z | | | I | 0-0 | 29-11-32 | D02246 | | | | | FA | | D08036J | 2 | | | ALL |
| 207B | 24 | PL | AC | 4-0 | 27-32-11 | D02674 | | 21 | | | | | D04885J | 3 | | | ALL |
| 207R | 24 | PL | AC | 0-0 | 27-32-11 | D02674 | | 19 | | | | | D04885J | 2 | | | ALL |
| 211B | 24 | PW | IK | 4-0 | 77-12-12 | D10064 | | 13 | | | | | TB0182Y | C018 | BJ | | 050-099, 162-199, 277-299 |
| 211B | 24 | PW | IK | 4-0 | 77-12-12 | D10064 | | 13 | | | | | TB0158Y | C026 | BJ | | 150-157, 275-276 |
| 211F | 20 | UA | | 3-0 | 77-12-12 | TB0182Y | | A017 | BJ | | | | GDX0001 | S.. | 2 | | 050-099, 280-299 |
| 211F | 20 | PA | | 0-6 | 77-12-12 | TB0158Z | | 28 | BJ | | | | GDX0001 | S.. | 2 | | 150-157 |
| 211F | 20 | UA | | 0-6 | 77-12-12 | TB0182Y | | A017 | BJ | | | | GDX0001 | S.. | 2 | | 162-199 |
| 211F | 20 | UA | | 2-0 | 77-12-12 | TB0158Z | | 28 | BJ | | | | GDX0001 | S.. | 2 | | 275-276 |
| 211F | 20 | UA | | 2-0 | 77-12-12 | TB0182Y | | A017 | BJ | | | | GDX0001 | S.. | 2 | | 277-278 |
| 211R | 24 | PW | IK | 0-0 | 77-12-12 | D10064 | | 9 | | | | | TB0182Y | A018 | BJ | | 050-099, 162-199, 277-299 |
| 211R | 24 | PW | IK | 0-0 | 77-12-12 | D10064 | | 9 | | | | | TB0158Y | A026 | BJ | | 150-157, 275-276 |
| 211Z | | | IK | 0-0 | 77-12-12 | TB0182Y | | REF | | FM | | | D10064 | DED | | | 050-099 |
| 211Z | | | IK | 0-0 | 77-12-12 | D10064 | | DED | | | | | TB0158Z | 28 | BJ | | 150-157, 275-276 |
| 211Z | | | IK | 0-0 | 77-12-12 | D10064 | | DED | | | | | TB0182Y | REF | | FN | 162-199, 277-299 |
| 212B | 24 | PW | IL | 4-0 | 77-12-12 | D10064 | | 20 | | | | | TB0182Y | C018 | BJ | | 050-099, 162-199, 277-299 |
| 212B | 24 | PW | IL | 4-0 | 77-12-12 | D10064 | | 20 | | | | | TB0158Y | C026 | BJ | | 150-157, 275-276 |
| 212R | 24 | PW | IL | 0-0 | 77-12-12 | D10064 | | 21 | | | | | TB0182Y | A018 | BJ | | 050-099, 162-199, 277-299 |
| 212R | 24 | PW | IL | 0-0 | 77-12-12 | D10064 | | 21 | | | | | TB0158Y | A026 | BJ | | 150-157, 275-276 |
| 212Z | | | IL | 0-0 | 77-12-12 | TB0182Y | | REF | | FN | | | D10064 | DED | | | 050-099 |
| 212Z | | | IL | 0-0 | 77-12-12 | D10064 | | DED | | | | | TB0158Z | 28 | BJ | | 150-157, 275-276 |
| 212Z | | | IL | 0-0 | 77-12-12 | D10064 | | DED | | | | | TB0182Y | REF | | FN | 162-199, 277-299 |
| 213B | 24 | PW | IM | 4-0 | 77-12-12 | D10062 | | 13 | | | | | TB0182Y | C013 | BJ | | 050-099, 162-199, 277-299 |
| 213B | 24 | PW | IM | 4-0 | 77-12-12 | D10062 | | 13 | | | | | TB0158Y | C025 | BJ | | 150-157, 275-276 |
| 213F | 20 | UA | | 3-0 | 77-12-12 | TB0182Y | | A014 | BJ | | | | GDX0002 | S.. | 2 | | 050-099, 280-299 |
| 213F | 20 | PA | | 0-6 | 77-12-12 | TB0158Z | | 27 | BJ | | | | GDX0002 | S.. | 2 | | 150-157 |
| 213F | 20 | UA | | 0-6 | 77-12-12 | TB0182Y | | A014 | BJ | | | | GDX0002 | S.. | 2 | | 162-199 |
| 213F | 20 | UA | | 2-0 | 77-12-12 | TB0158Z | | 27 | BJ | | | | GDX0002 | S.. | 2 | | 275-276 |
| 213F | 20 | UA | | 2-0 | 77-12-12 | TB0182Y | | A014 | BJ | | | | GDX0002 | S.. | 2 | | 277-278 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1114 | 286T1114 | | | ELECTRICAL SYSTEMS CARD FILE P50 (continued) | | | | | | | | | | | |
| 213R | 24 | PW | IM | 0-0 | 77-12-12 | D10062 | | 9 | | | TB0182Y | A013 | BJ | | 050-099, 162-199, 277-299 |
| 213R | 24 | PW | IM | 0-0 | 77-12-12 | D10062 | | 9 | | | TB0158Y | A025 | BJ | | 150-157, 275-276 |
| 213Z | | | IM | 0-0 | 77-12-12 | TB0182Y | REF | | FM | | D10062 | DED | | | 050-099 |
| 213Z | | | IM | 0-0 | 77-12-12 | D10062 | DED | | | | TB0158Z | 27 | BJ | | 150-157, 275-276 |
| 213Z | | | IM | 0-0 | 77-12-12 | D10062 | DED | | | | TB0182Y | REF | | FM | 162-199, 277-299 |
| 214B | 24 | PW | IN | 4-0 | 77-12-12 | D10062 | | 20 | | | TB0182Y | C013 | BJ | | 050-099, 162-199, 277-299 |
| 214B | 24 | PW | IN | 4-0 | 77-12-12 | D10062 | | 20 | | | TB0158Y | C025 | BJ | | 150-157, 275-276 |
| 214R | 24 | PW | IN | 0-0 | 77-12-12 | D10062 | | 21 | | | TB0182Y | A013 | BJ | | 050-099, 162-199, 277-299 |
| 214R | 24 | PW | IN | 0-0 | 77-12-12 | D10062 | | 21 | | | TB0158Y | A025 | BJ | | 150-157, 275-276 |
| 214Z | | | IN | 0-0 | 77-12-12 | TB0182Y | REF | | FM | | D10062 | DED | | | 050-099 |
| 214Z | | | IN | 0-0 | 77-12-12 | D10062 | DED | | | | TB0158Z | 27 | BJ | | 150-157, 275-276 |
| 214Z | | | IN | 0-0 | 77-12-12 | D10062 | DED | | | | TB0182Y | REF | | FM | 162-199, 277-299 |
| 301B | 24 | PM | C | 4-0 | 27-58-21 | D02674 | | 12 | | | D08028J | 6 | | | ALL |
| 301R | 24 | PM | C | 0-0 | 27-58-21 | D02674 | | 13 | | | D08028J | 7 | | | ALL |
| 301Y | 24 | PM | C | 0-0 | 27-58-21 | D02674 | | 11 | | | D08028J | 8 | | | ALL |
| 304B | 24 | PM | AB | 4-0 | 27-58-21 | D02674 | | 32 | | | D08028J | 13 | | | ALL |
| 304R | 24 | PM | AB | 0-0 | 27-58-21 | D02674 | | 33 | | | D08028J | 14 | | | ALL |
| 304Y | 24 | PM | AB | 0-0 | 27-58-21 | D02674 | | 34 | | | D08028J | 15 | | | ALL |
| FRA | | | | 0-0 | 28-21-12 | D08038J | | | FD | | D08038J | 2 | | | ALL |
| FRB | | | | 0-0 | 28-21-12 | D08038J | | | FD | | D08038J | 7 | | | ALL |
| FRC | | | | 0-0 | 28-21-12 | D08038J | | | FD | | D08038J | 9 | | | ALL |
| FRD | | | | 0-0 | 28-21-12 | D08038J | | | FE | | D08038J | 3 | | | ALL |
| FRE | | | | 0-0 | 28-21-12 | D08038J | | | FE | | D08038J | 10 | | | ALL |
| FRF | | | | 0-0 | 28-21-12 | D08038J | | | FE | | D08038J | 12 | | | ALL |
| FRM | | | | 0-0 | 77-12-12 | TB0182Y | REF | | FM | | TB0182Y | A014 | BJ | | 050-099, 162-199, 277-299 |
| FRN | | | | 0-0 | 77-12-12 | TB0182Y | REF | | FN | | TB0182Y | A017 | BJ | | 050-099, 162-199, 277-299 |
| PA1 | | | | 0-0 | 27-58-21 | D02674 | | 47 | | | D02674 | 66 | | | 050-099 |
| PA1 | | | | 0-0 | 99-99-99 | D02674 | | 47 | | | D02674 | 66 | | | 150-154 |
| PA1 | | | | 0-0 | 27-58-21 | D02674 | | 47 | | | D02674 | 64 | | | 155-199, 275-299 |
| PB1 | | | | 0-0 | 99-99-99 | D01882 | | 1 | | | D01882 | 41 | | | ALL |
| PC1 | | | | 0-0 | 99-99-99 | D02246 | | 2 | | | D02246 | 26 | | | ALL |
| PD1 | | | | 2-0 | 73-21-18 | D10062 | | 44 | | | D10062 | 52 | | | ALL |
| PE1 | | | | 2-0 | 73-21-18 | D10064 | | 44 | | | D10064 | 52 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|-----------------------------------|-------|-----|-------------|---------|-------|------|------|--------|---------|------|------|--------|--|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1115 | 286T1115 | ATTENDANT CALL LIGHT-RIGHT | | | | | | | | | | | | | | |
| 001 | 22 | PA | | 6-0 | 23-42-11 | D06055P | | 1 | | | L00211 | = P | \$ | | 050-099, 150-154, 156, 162-199, 277-299 | |
| 002 | 22 | PA | | 6-0 | 23-34-13 | D06055P | | 2 | | | L00582 | = P | \$ | | 050-099, 150-154, 156, 162-199 | |
| 002 | 22 | PA | | 6-0 | 23-34-13 | D06055P | | 2 | | | L00688 | = P | \$ | | 277-278 | |
| 002 | 22 | PA | | 6-0 | 23-34-13 | D06055P | | 2 | | | L00686 | = P | \$ | | 280-299 | |
| 003 | 22 | PA | | 6-0 | 33-25-11 | D06055P | | 3 | | | L01196 | = P | \$ | | 050-099 | |
| 003 | 22 | PA | | 6-0 | 33-25-11 | D06055P | | 3 | | | L01088 | = P | \$ | | 150-154, 156, 162-199 | |
| 003 | 22 | PA | | 6-0 | 33-25-11 | D06055P | | 3 | | | L01160 | = P | \$ | | 277-299 | |
| 004 | 20 | PA | | 6-0 | 23-42-11 | D06055P | | 4 | | | L00211 | = G | \$ | | 050-099, 150-154, 156, 162-199, 277-299 | |
| W1116 | 286T1116 | R WW SERVICE PNL-P56 | | | | | | | | | | | | | | |
| 001 | 18 | UA | | 2-0 | 33-31-11 | D05810J | | 4 | | | S00319 | | 2 | L | ALL | |
| 002 | 18 | UA | | 2-0 | 33-31-11 | D05810J | | 5 | | | S00319 | | 1 | L | ALL | |
| 003 | 18 | UA | | 2-0 | 33-31-11 | D05810J | | 6 | | | S00319 | | 3 | L | ALL | |
| A-A | | | | 0-0 | 23-41-11 | D05810J | | 1 | | | D08553 | RED | | | ALL | |
| A-B | | | | 0-0 | 23-41-11 | D05810J | | 2 | | | D08553 | BLU | | | ALL | |
| A-C | | | | 0-0 | 23-41-11 | D05810J | | 3 | | | D08553 | BLK | | | ALL | |
| W1117 | 286T1117 | ATTENDANT CALL LIGHT-LEFT | | | | | | | | | | | | | | |
| 001 | 22 | PA | | 6-0 | 23-42-11 | D06059P | | 1 | | | L01118 | = P | \$ | | 050-099, 150-199 | |
| 002 | 22 | PA | | 6-0 | 23-34-13 | D06059P | | 2 | | | L01133 | = P | \$ | | 050-099, 150-199 | |
| 003 | 22 | PA | | 6-0 | 33-25-11 | D06059P | | 3 | | | L01161 | = P | \$ | | 050-099, 150-199 | |
| 004 | 20 | PA | | 6-0 | 23-42-11 | D06059P | | 4 | | | L01118 | = G | \$ | | 050-099, 150-199 | |
| W1118 | 286T1118 | P37-R1A-INTEGRATION | | | | | | | | | | | | | | |
| 002 | 22 | PA | | 6-0 | 27-81-21 | K00221 | | X1 | C | | TB0274Y | C003 | BJ | | ALL | |
| 003 | 18 | PA | | 6-0 | 27-81-21 | K00221 | | B1 | C | | TB0274G | | 5 | 2 | ALL | |
| 004 | 18 | PA | | 6-0 | 27-81-21 | K00221 | | C1 | C | | TB0274G | | 6 | 2 | ALL | |
| 005 | 18 | PA | | 6-0 | 27-81-21 | K00221 | | A1 | C | | TB0274G | | 7 | 2 | ALL | |
| 006 | 18 | PA | | 2-0 | 27-81-21 | K00221 | | A2 | C | | K00222 | A3 | C | | ALL | |
| 007 | 18 | PA | | 2-0 | 27-81-21 | K00221 | | B2 | C | | K00222 | B3 | C | | ALL | |
| 008 | 18 | PA | | 2-0 | 27-81-21 | K00221 | | C2 | C | | K00222 | C3 | C | | ALL | |
| 009 | 18 | PA | | 6-0 | 27-81-21 | TB0274G | | 7 | 2 | | K00222 | A1 | C | | ALL | |
| 010 | 18 | PA | | 2-0 | 27-81-21 | K00223 | | A1 | C | | K00222 | A2 | C | | ALL | |
| 011 | 18 | PA | | 2-0 | 27-81-21 | K00223 | | B1 | C | | K00222 | B2 | C | | ALL | |
| 012 | 18 | PA | | 2-0 | 27-81-21 | K00223 | | C1 | C | | K00222 | C2 | C | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1118 | 286T1118 | | | P37-R1A-INTEGRATION (continued) | | | | | | | | | | | |
| 013 | 18 | PA | | 6-0 | 27-81-21 | TB0274G | 6 | 2 | | K00222 | B1 | C | | ALL | |
| 014 | 18 | PA | | 6-0 | 27-81-21 | TB0274G | 5 | 2 | | K00222 | C1 | C | | ALL | |
| 015 | 22 | PA | | 6-0 | 27-81-21 | TB0274Y | C003 | BJ | | K00222 | X1 | C | | ALL | |
| 016 | 22 | PA | | 8-0 | 27-81-11 | TB0254Y | C001 | BJ | | D04412J | 1 | | | ALL | |
| 017 | 22 | PA | | 8-0 | 27-81-11 | TB0254Y | C002 | BJ | | D04412J | 2 | | | ALL | |
| 018 | 22 | PA | | 8-0 | 27-81-11 | TB0254Y | A001 | BJ | | D04412J | 3 | | | ALL | |
| 020 | 20 | PA | | 2-0 | 27-81-21 | K00223 | X2 | C | | GDX0009 | D.. | 2 | | ALL | |
| 021 | 18 | PA | | 9-0 | 27-81-21 | K00223 | A2 | C | | D05862J | 1 | | | ALL | |
| 022 | 18 | PA | | 9-0 | 27-81-21 | K00223 | B2 | C | | D05862J | 2 | | | ALL | |
| 023 | 18 | PA | | 9-0 | 27-81-21 | K00223 | C2 | C | | D05862J | 3 | | | ALL | |
| 024 | 22 | PA | | 2-0 | 27-81-11 | D02278 | A2 | | | D02280 | A3 | | | ALL | |
| 025 | 22 | PA | | 2-0 | 27-81-11 | D02278 | B2 | | | D02280 | B3 | | | ALL | |
| 026 | 22 | PA | | 2-0 | 27-81-11 | D02278 | C2 | | | D02280 | C3 | | | ALL | |
| 027 | 22 | PA | | 7-0 | 27-81-11 | D02278 | X2 | | | TB0190X | B004 | BJ | | ALL | |
| 028 | 22 | PA | | 2-0 | 27-81-11 | D02282 | A1 | | | D02280 | A2 | | | ALL | |
| 029 | 22 | PA | | 2-0 | 27-81-11 | D02282 | B1 | | | D02280 | B2 | | | ALL | |
| 030 | 22 | PA | | 2-0 | 27-81-11 | D02282 | C1 | | | D02280 | C2 | | | ALL | |
| 031 | 20 | PA | | 7-0 | 27-81-11 | D02282 | A2 | | | D05862J | 4 | | | ALL | |
| 032 | 20 | PA | | 7-0 | 27-81-11 | D02282 | B2 | | | D05862J | 5 | | | ALL | |
| 033 | 20 | PA | | 7-0 | 27-81-11 | D02282 | C2 | | | D05862J | 6 | | | ALL | |
| 034 | 22 | PA | | 4-0 | 27-81-11 | D02280 | A1 | | | TB0254Y | C001 | BJ | | ALL | |
| 035 | 22 | PA | | 4-0 | 27-81-11 | D02280 | B1 | | | TB0254Y | A001 | BJ | | ALL | |
| 036 | 22 | PA | | 4-0 | 27-81-11 | D02280 | C1 | | | TB0254Y | C002 | BJ | | ALL | |
| 037 | 22 | PA | | 4-0 | 27-81-11 | D02280 | X1 | | | TB0254Y | A002 | BJ | | ALL | |
| 038 | 22 | PA | | 4-0 | 27-81-11 | D02278 | A1 | | | TB0254Y | C001 | BJ | | ALL | |
| 039 | 22 | PA | | 4-0 | 27-81-11 | D02278 | C1 | | | TB0254Y | A001 | BJ | | ALL | |
| 040 | 22 | PA | | 4-0 | 27-81-11 | D02278 | B1 | | | TB0254Y | C002 | BJ | | ALL | |
| 041 | 22 | PA | | 4-0 | 27-81-11 | D02278 | X1 | | | TB0254Y | A002 | BJ | | ALL | |
| 042 | 18 | PA | | 6-0 | 27-81-21 | D08064J | 1 | | | TB0274G | 7 | 2 | | ALL | |
| 043 | 18 | PA | | 6-0 | 27-81-21 | D08064J | 3 | | | TB0274G | 6 | 2 | | ALL | |
| 044 | 18 | PA | | 6-0 | 27-81-21 | D08064J | 2 | | | TB0274G | 5 | 2 | | ALL | |
| 046 | 20 | PA | | 3-0 | 27-81-11 | D02282 | X2 | | | GDX0001 | D.. | 2 | | ALL | |
| 047 | 22 | PQ | H | 7-0 | 27-81-11 | D02282 | X1 | | | TB0190F | C008 | 2 | | ALL | |
| 047Z | | | H | 0-0 | 27-81-11 | D02282 | DED | | | TB0190F | DED | | | ALL | |
| 048 | 22 | PA | | 7-0 | 27-81-11 | D02280 | X2 | | | TB0190X | A004 | BJ | | ALL | |
| 049 | 24 | PK | | 6-0 | 21-44-11 | D04924J | 10 | | | D04296J | 13 | | | ALL | |
| 050 | 22 | PA | | 4-0 | 21-44-11 | D04296J | 14 | | | TB0304Y | A011 | BJ | | ALL | |
| 051 | 24 | PK | | 6-0 | 21-44-11 | D04924J | 12 | | | D04296J | 20 | | | ALL | |
| 052 | 24 | PK | | 4-0 | 21-44-11 | TB0304Y | C011 | BJ | | D04296J | 28 | | | ALL | |

WIRE LIST

D280T132

91-21-11
 Section W1110
 Page 13
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1118 | 286T1118 | | | P37-R1A-INTEGRATION (continued) | | | | | | | | | | | | | | |
| 053 | 24 | | PK | 4-0 | 21-25-21 | D04922J | | | | 5 | | | | TB0304X | A001 | BJ | | ALL |
| 054 | 12 | | PA | 5-0 | 21-25-21 | D04922J | | | | 16 | | | | K00416 | A1 | E | | ALL |
| 055 | 12 | | PA | 5-0 | 21-25-21 | D04922J | | | | 18 | | | | K00416 | B1 | E | | ALL |
| 056 | 12 | | PA | 5-0 | 21-25-21 | D04922J | | | | 14 | | | | K00416 | C1 | E | | ALL |
| 057 | 24 | | PK | 6-0 | 21-43-11 | D03680 | | | | A1 | | | | D04924J | 7 | | | 050-099, 275-299 |
| 057 | 24 | | PK | 8-0 | 21-43-11 | D03680 | | | | A1 | | | | D04924J | 7 | | | 150-199 |
| 059 | 24 | | PK | 6-0 | 21-43-11 | D03680 | | | | A3 | | | | D04924J | 8 | | | 050-099 |
| 059 | 24 | | PK | 8-0 | 21-43-11 | D03680 | | | | A3 | | | | D04924J | 8 | | | 150-199 |
| 059 | 24 | | PK | 7-0 | 21-43-11 | D03680 | | | | A3 | | | | D04924J | 8 | | | 275-299 |
| 060 | 24 | | PK | 7-0 | 21-43-11 | D03680 | | | | X2 | | | | D04296J | 17 | | | 050-099 |
| 060 | 24 | | PK | 6-0 | 21-43-11 | D03680 | | | | X2 | | | | D04296J | 17 | | | 150-199, 275-299 |
| 065 | 24 | | PK | 9-0 | 21-43-11 | D04296J | | | | 11 | | | | D13806 | B2 | | | ALL |
| 066 | 12 | | PA | 6-0 | 38-32-11 | D05760J | | | | 1 | | | | TB5078 | 5 | C | | ALL |
| 067 | 12 | | PA | 6-0 | 38-32-11 | D05760J | | | | 2 | | | | TB5078 | 6 | C | | ALL |
| 068 | 12 | | PA | 6-0 | 38-32-11 | D05760J | | | | 3 | | | | TB5078 | 7 | C | | ALL |
| 071 | 22 | | PA | 5-0 | 21-26-21 | D00976 | | | | C2 | | | | TB0274X | B012 | BJ | | ALL |
| 072 | 22 | | PA | 6-0 | 21-26-21 | D00976 | | | | B2 | | | | TB0192X | D019 | BJ | | ALL |
| 073 | 22 | | PA | 5-0 | 21-26-21 | D00976 | | | | A2 | | | | TB0274X | A012 | BJ | | ALL |
| 074 | 24 | | PK | 5-0 | 21-26-21 | D00976 | | | | X1 | | | | TB0274Y | C010 | BJ | | ALL |
| 075 | 22 | | PA | 6-0 | 21-26-21 | D00976 | | | | C1 | | | | D04922J | 19 | | | ALL |
| 076 | 22 | | PA | 6-0 | 21-26-21 | D00976 | | | | B1 | | | | D04922J | 21 | | | ALL |
| 077 | 22 | | PA | 5-0 | 21-26-21 | D00976 | | | | A1 | | | | TB0192X | C002 | BJ | | ALL |
| 079 | 22 | | PA | 6-0 | 21-44-21 | D04296J | | | | 41 | | | | D04922J | 25 | | | ALL |
| 080 | 22 | | PA | 6-0 | 21-44-21 | D04296J | | | | 42 | | | | D04922J | 15 | | | ALL |
| 081 | 22 | | PA | 4-0 | 21-44-11 | D04924J | | | | 11 | | | | TB0304Y | A011 | BJ | | ALL |
| 08B | 20 | | PA | 7-0 | 30-71-24 | D05692J | | | | 10 | | | | TB0210Y | A001 | BJ | | 050-099 |
| 092 | 20 | | PA | 6-0 | 30-71-24 | TB0210Y | | | | A004 | BJ | | | D05692J | 13 | | | 150-154 |
| 092 | 20 | | PA | 6-0 | 30-71-24 | TB0320Y | | | | A011 | BJ | | | D05692J | 13 | | | 155-199 |
| 094 | 20 | | PA | 6-0 | 30-71-24 | TB0210Y | | | | A004 | BJ | | | D05692J | 10 | | | 150-154 |
| 094 | 20 | | PA | 6-0 | 30-71-24 | TB0320Y | | | | A011 | BJ | | | D05692J | 10 | | | 155-199 |
| 095 | 20 | | PA | 6-0 | 30-71-24 | TB0210X | | | | C010 | BJ | | | D05692J | 2 | | | 150-199 |
| 096 | 20 | | PA | 6-0 | 21-31-21 | D04296J | | | | 27 | | | | D05692J | 7 | | | ALL |
| 097 | 12 | | PA | 4-0 | 21-25-21 | K00416 | | | | A2 | E | | | TB5078 | 8 | C | | ALL |
| 098 | 12 | | PA | 4-0 | 21-25-21 | K00416 | | | | B2 | E | | | TB5078 | 9 | C | | ALL |
| 099 | 12 | | PA | 4-0 | 21-25-21 | K00416 | | | | C2 | E | | | TB5078 | 10 | C | | ALL |
| 100 | 20 | | PA | 7-0 | 30-41-12 | D04296J | | | | 39 | | | | TB0192X | C011 | BJ | | ALL |
| 101 | 20 | | PA | 7-0 | 30-41-12 | D04296J | | | | 38 | | | | TB0192X | D011 | BJ | | ALL |
| 103 | 20 | | PA | 7-0 | 25-33-11 | D11394 | | | | A3 | | | | TB0192X | A011 | BJ | | 153-154 |
| 104 | 20 | | PA | 3-0 | 25-33-11 | D11394 | | | | B1 | | | | GDX0002 | D.. | 2 | | 153-154 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1118 | 286T1118 | | | P37-R1A-INTEGRATION (continued) | | | | | | | | | | | |
| 105 | 22 | | PA | | 4-0 | 25-33-11 | D11394 | | B2 | | TB0088D | A007 | 2 | | 153-154 |
| 106 | 20 | | PA | | 4-0 | 25-33-11 | D11394 | | X1 | | TB0254Z | 16 | BJ | | 153-154 |
| 106 | 20 | | PA | | 6-0 | 25-33-11 | D11394 | | X1 | | TB0212Y | C005 | BJ | | 155-157, 165-199 |
| 106 | 20 | | PA | | 4-0 | 25-33-11 | D11394 | | X1 | | TB0212Y | C005 | BJ | | 162-164 |
| 106 | 20 | | PA | | 6-0 | 25-33-11 | D13940 | | X1 | | TB0212Y | C005 | BJ | | 277-299 |
| 107 | 22 | | PA | | 4-0 | 25-33-11 | TB0088D | | A007 | 2 | D11394 | | X2 | | 153-154 |
| 107 | 22 | | PA | | 4-0 | 25-33-11 | TB0088D | | A004 | 2 | D11394 | | X2 | | 155-199 |
| 107 | 22 | | PA | | 4-0 | 25-33-11 | TB0088D | | A004 | 2 | D13940 | | X2 | | 277-299 |
| 109 | 22 | | PA | | 1-0 | 25-33-11 | TB0088D | | A003 | 2 | TB0088D | C007 | 2 | | 153-154 |
| 110 | 22 | | PA | | 1-0 | 25-33-11 | TB0088D | | C007 | 2 | TB0088D | C004 | 2 | | 153-154 |
| 11A | 22 | | PA | | 15-0 | 21-26-31 | C00358 | | A1 | D | D13422 | | A2 | | 050-099 |
| 11A | 22 | | PA | | 20-0 | 21-26-31 | C00358 | | A1 | D | D13422 | | A2 | | 150-199, 275-278 |
| 11A | 22 | | PA | | 20-0 | 21-26-31 | C00358 | | REF | + | D13422 | | A2 | | 280-299 |
| 11B | 22 | | PA | | 9-0 | 21-26-31 | C00358 | | B1 | D | D13422 | | B2 | | 050-099 |
| 11B | 22 | | PA | | 13-0 | 21-26-31 | C00358 | | B1 | D | D13422 | | B2 | | 150-199, 275-278 |
| 11B | 22 | | PA | | 14-0 | 21-26-31 | C00358 | | REF | + | D13422 | | B2 | | 280-299 |
| 11C | 22 | | PA | | 9-0 | 21-26-31 | C00358 | | C1 | D | D13422 | | C2 | | 050-099 |
| 11C | 22 | | PA | | 13-0 | 21-26-31 | C00358 | | C1 | D | D13422 | | C2 | | 150-199, 275-278 |
| 11C | 22 | | PA | | 14-0 | 21-26-31 | C00358 | | REF | + | D13422 | | C2 | | 280-299 |
| 11D | 22 | | PA | | 17-0 | 21-26-31 | C00359 | | A1 | D | D13424 | | A2 | | 050-099 |
| 11D | 22 | | PA | | 13-0 | 21-26-31 | C00359 | | A1 | D | D13424 | | A2 | | 150-199, 275-299 |
| 11E | 22 | | PA | | 10-0 | 21-26-31 | C00359 | | B1 | D | D13424 | | B2 | | 050-099 |
| 11E | 22 | | PA | | 12-0 | 21-26-31 | C00359 | | B1 | D | D13424 | | B2 | | 150-199, 275-299 |
| 11F | 22 | | PA | | 10-0 | 21-26-31 | C00359 | | C1 | D | D13424 | | C2 | | 050-099 |
| 11F | 22 | | PA | | 12-0 | 21-26-31 | C00359 | | C1 | D | D13424 | | C2 | | 150-199, 275-299 |
| 11G | 22 | | PA | | 7-0 | 21-26-31 | D06658J | | 4 | | D13422 | | A1 | | 050-099 |
| 11G | 22 | | PA | | 9-0 | 21-26-31 | D13422 | | A1 | | D06658J | | 4 | | 150-199, 275-299 |
| 11H | 22 | | PA | | 7-0 | 21-26-31 | D06658J | | 5 | | D13422 | | B1 | | 050-099 |
| 11H | 22 | | PA | | 9-0 | 21-26-31 | D13422 | | B1 | | D06658J | | 5 | | 150-199, 275-299 |
| 11J | 22 | | PA | | 7-0 | 21-26-31 | D06658J | | 6 | | D13422 | | C1 | | 050-099 |
| 11J | 22 | | PA | | 9-0 | 21-26-31 | D13422 | | C1 | | D06658J | | 6 | | 150-199, 275-299 |
| 11K | 24 | | PK | | 7-0 | 21-26-31 | D06658J | | 7 | | D13422 | | X2 | | 050-099 |
| 11K | 24 | | PK | | 9-0 | 21-26-31 | D13422 | | X2 | | D06658J | | 7 | | 150-199, 275-299 |
| 11L | 22 | | PA | | 7-0 | 21-26-31 | D05692J | | 12 | | D13424 | | A1 | | 050-099 |
| 11L | 22 | | PA | | 9-0 | 21-26-31 | D13424 | | A1 | | D05692J | | 12 | | 150-199, 275-299 |
| 11M | 22 | | PA | | 7-0 | 21-26-31 | D05692J | | 2 | | D13424 | | B1 | | 050-099 |
| 11M | 22 | | PA | | 9-0 | 21-26-31 | D13424 | | B1 | | D05692J | | 14 | | 150-199, 275-299 |
| 11N | 22 | | PA | | 7-0 | 21-26-31 | D05692J | | 15 | | D13424 | | C1 | | 050-099 |
| 11N | 22 | | PA | | 9-0 | 21-26-31 | D13424 | | C1 | | D05692J | | 15 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1118 | 286T1118 | | | P37-R1A-INTEGRATION (continued) | | | | | | | | | | | | | | |
| 11P | 24 | | PK | 7-0 | 21-26-31 | D05692J | | | | 16 | | | | D13424 | X2 | | | 050-099 |
| 11P | 24 | | PK | 9-0 | 21-26-31 | D13424 | | | | X2 | | | | D05692J | 16 | | | 150-199, 275-299 |
| 11R | 20 | | PA | 7-0 | 21-26-31 | SP03680 | | | | | | W | | GDX0009 | D.. | 2 | | 050-099 |
| 11R | 20 | | PA | 10-0 | 21-26-31 | SP03680 | | | | | | W | | GDX0010 | D.. | P | | 150-154 |
| 11R | 20 | | PA | 12-0 | 21-26-31 | SP03680 | | | | | | W | | GDX0009 | D.. | 2 | | 155-199, 277-299 |
| 11R | 20 | | PA | 10-0 | 21-26-31 | SP03680 | | | | | | W | | GDX0010 | D.. | F | | 275 |
| 11R | 20 | | PA | 10-0 | 21-26-31 | SP03680 | | | | | | W | | GDX0009 | D.. | 2 | | 276 |
| 11S | 20 | | PA | 3-0 | 21-26-31 | SP03684 | | | | | | W | | GDX0009 | D.. | 2 | | 050-099 |
| 11S | 20 | | PA | 10-0 | 21-26-31 | SP03684 | | | | | | W | | GDX0010 | D.. | P | | 150-154 |
| 11S | 20 | | PA | 8-0 | 21-26-31 | SP03684 | | | | | | W | | GDX0009 | D.. | 2 | | 155-199, 277-299 |
| 11S | 20 | | PA | 10-0 | 21-26-31 | SP03684 | | | | | | W | | GDX0010 | D.. | F | | 275 |
| 11S | 20 | | PA | 10-0 | 21-26-31 | SP03684 | | | | | | W | | GDX0009 | D.. | 2 | | 276 |
| 11T | 20 | | PA | 10-0 | 21-26-31 | D06658J | | | | 1 | | | | GDX0009 | D.. | 2 | | 050-099 |
| 11T | 20 | | PA | 6-0 | 21-26-31 | GDX0010 | | | | | D.. | F | | D06658J | 1 | | | 150-154, 275 |
| 11T | 20 | | PA | 10-0 | 21-26-31 | GDX0009 | | | | | D.. | 2 | | D06658J | 1 | | | 155-199, 277-299 |
| 11T | 20 | | PA | 6-0 | 21-26-31 | GDX0009 | | | | | D.. | 2 | | D06658J | 1 | | | 276 |
| 11U | 24 | | PK | 7-0 | 21-26-31 | D06658J | | | | 3 | | | | SP03682 | | W | | 050-099 |
| 11U | 24 | | PK | 7-0 | 21-26-31 | SP03682 | | | | | | W | | D06658J | 3 | | | 150-199, 275-299 |
| 11V | 24 | | PK | 8-0 | 21-26-31 | D13424 | | | | X1 | | | | TB0320D | C003 | 2 | | 050-099 |
| 11V | 24 | | PK | 10-0 | 21-26-31 | TB0314Z | | | | 7 | BJ | | | D13424 | X1 | | | 150-154, 275 |
| 11V | 24 | | PK | 8-0 | 21-26-31 | TB0320D | | | | C003 | 2 | | | D13424 | X1 | | | 155-199, 276-299 |
| 11W | 24 | | PK | 5-0 | 21-26-31 | D06658J | | | | 2 | | | | D05692J | 17 | | | ALL |
| 11X | 24 | | PK | 4-0 | 21-26-31 | D13422 | | | | X1 | | | | TB0314Z | CAP | Y | | 050-099 |
| 11X | 24 | | PK | 4-0 | 21-26-31 | TB0314Z | | | | CAP | Y | | | D13422 | X1 | | | 150-199, 277-299 |
| 11X | 24 | | PK | 16-0 | 21-26-31 | TB0314Z | | | | CAP | Y | | | D13422 | X1 | | | 275-276 |
| 11Y | 22 | | PQ | M | 10-0 | 21-28-11 | D05692J | | | 18 | | | | TB0314X | A009 | BJ | | 050-099 |
| 11Y | 22 | | PA | M | 10-0 | 21-28-11 | D05692J | | | 18 | | | | TB0314X | A009 | BJ | | 150-199, 275-276 |
| 11YZ | | | | M | 0-0 | 21-28-11 | D05692J | | | DED | | | | TB0314X | DED | | | 050-099 |
| 126 | 20 | | PA | 6-0 | 36-11-41 | D04922J | | | | 4 | | | | D04296J | 15 | | | ALL |
| 127 | 24 | | PK | 4-0 | 21-51-21 | D04922J | | | | 1 | | | | TB0304X | C001 | BJ | | ALL |
| 128 | 24 | | PK | 4-0 | 21-51-21 | D04922J | | | | 2 | | | | TB0304X | D001 | BJ | | ALL |
| 129 | 24 | | PK | 4-0 | 21-51-21 | D04922J | | | | 3 | | | | TB0304X | A002 | BJ | | ALL |
| 12A | 24 | | PK | 5-0 | 21-43-11 | D04924J | | | | 9 | | | | D06658J | 19 | | | ALL |
| 12B | 24 | | PK | 5-0 | 21-43-11 | D04922J | | | | 9 | | | | D06658J | 20 | | | ALL |
| 12D | 24 | | PK | 5-0 | 21-43-11 | D04924J | | | | 21 | | | | D06658J | 21 | | | ALL |
| 12F | 24 | | PK | 7-0 | 21-43-11 | D04922J | | | | 7 | | | | TB0210X | C020 | BJ | | ALL |
| 12G | 24 | | PK | 7-0 | 21-43-11 | D04922J | | | | 8 | | | | TB0210X | B020 | BJ | | ALL |
| 12H | 24 | | PK | 7-0 | 21-43-11 | D04922J | | | | 10 | | | | TB0210X | A020 | BJ | | ALL |
| 12J | 24 | | PK | 7-0 | 21-51-11 | D06658J | | | | 18 | | | | TB0192X | B002 | BJ | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1118 | 286T1118 | | | P37-R1A-INTEGRATION (continued) | | | | | | | | | | | |
| 12J | 24 | | PK | | 7-0 | 21-51-11 | TB0192X | B002 | BJ | | D06658J | 18 | | | 150-199, 275-299 |
| 12K | 24 | | PK | | 10-0 | 21-28-11 | D13428 | | X1 | | TB0314Z | 7 | BJ | | 050-099 |
| 12K | 24 | | PK | | 13-0 | 21-28-11 | TB0314Z | | 7 | BJ | D13428 | | X1 | | 150-199, 275-299 |
| 12L | 22 | | PA | | 9-0 | 21-28-11 | C00666 | | 1 | D | D13426 | | A2 | | 050-099 |
| 12L | 22 | | PA | | 14-0 | 21-28-11 | C00666 | | 1 | D | D13426 | | A2 | | 150-199, 275-299 |
| 12M | 22 | | PA | | 9-0 | 21-28-11 | C00665 | | 1 | D | D13430 | | A2 | | 050-099 |
| 12M | 22 | | PA | | 14-0 | 21-28-11 | C00665 | | 1 | D | D13430 | | A2 | | 150-199, 275-299 |
| 12N | 22 | | PA | | 8-0 | 21-28-11 | D05692J | | 22 | | D13430 | | A1 | | 050-099 |
| 12N | 22 | | PA | | 9-0 | 21-28-11 | D13430 | | A1 | | D05692J | | 22 | | 150-199, 275-299 |
| 12P | 22 | | PA | | 8-0 | 21-28-11 | D05692J | | 20 | | D13430 | | A3 | | 050-099 |
| 12P | 22 | | PA | | 9-0 | 21-28-11 | D13430 | | A3 | | D05692J | | 20 | | 150-199, 275-299 |
| 12R | 22 | | PQ | X | 8-0 | 21-28-11 | D06658J | | 17 | | D13428 | | A1 | | 050-099 |
| 12R | 22 | | PA | | 9-0 | 21-28-11 | D13428 | | A1 | | D06658J | | 17 | | 150-199, 275-299 |
| 12RZ | | | | X | 0-0 | 21-28-11 | D06658J | | DED | | D13428 | | DED | | 050-099 |
| 12S | 22 | | PQ | J | 8-0 | 21-28-11 | D06658J | | 16 | | D13428 | | A3 | | 050-099 |
| 12S | 22 | | PA | | 9-0 | 21-28-11 | D13428 | | A3 | | D06658J | | 16 | | 150-199, 275-299 |
| 12SZ | | | | J | 0-0 | 21-28-11 | D06658J | | DED | | D13428 | | DED | | 050-099 |
| 12T | 24 | | PK | | 8-0 | 21-28-11 | D06658J | | 10 | | D13426 | | X2 | | 050-099 |
| 12T | 24 | | PK | | 9-0 | 21-28-11 | D13426 | | X2 | | D06658J | | 10 | | 150-199, 275-299 |
| 12U | 22 | | PA | | 8-0 | 21-28-11 | D06658J | | 15 | | D13426 | | A1 | | 050-099 |
| 12U | 22 | | PA | | 9-0 | 21-28-11 | D13426 | | A1 | | D06658J | | 15 | | 150-199, 275-299 |
| 12V | 22 | | PA | | 8-0 | 21-28-11 | D06658J | | 14 | | D13426 | | A3 | | 050-099 |
| 12V | 22 | | PA | | 9-0 | 21-28-11 | D13426 | | A3 | | D06658J | | 14 | | 150-199, 275-299 |
| 12W | 24 | | PK | | 8-0 | 21-28-11 | D06658J | | 12 | | D13430 | | X2 | | 050-099 |
| 12W | 24 | | PK | | 9-0 | 21-28-11 | D13430 | | X2 | | D06658J | | 12 | | 150-199, 275-299 |
| 12X | 24 | | PK | | 5-0 | 21-28-11 | D06658J | | 9 | | D05692J | | 24 | | 050-099 |
| 12X | 24 | | PK | | 5-0 | 21-28-11 | D05692J | | 24 | | D06658J | | 9 | | 150-199, 275-299 |
| 12Y | 24 | | PK | | 10-0 | 21-28-11 | D13426 | | X1 | | TB0314Z | | 7 | BJ | 050-099 |
| 12Y | 24 | | PK | | 13-0 | 21-28-11 | TB0314Z | | 7 | BJ | D13426 | | X1 | | 150-199, 275-299 |
| 130 | 24 | | PK | | 4-0 | 21-51-21 | D04922J | | 17 | | TB0304X | | B002 | BJ | 050-099 |
| 130 | 24 | | PK | | 4-0 | 21-51-21 | D04922J | | 17 | | TB0304Y | | A017 | BJ | 150-199, 275-299 |
| 134 | 14 | | PA | | 6-0 | 21-26-11 | D04924J | | 24 | | K00346 | | A2 | E | ALL |
| 135 | 14 | | PA | | 6-0 | 21-26-11 | D04924J | | 20 | | K00346 | | C2 | E | ALL |
| 136 | 14 | | PA | | 6-0 | 21-26-11 | D04924J | | 22 | | K00346 | | B2 | E | ALL |
| 137 | 24 | | PK | | 4-0 | 21-26-11 | D04924J | | 19 | | TB0304X | | B001 | BJ | ALL |
| 13A | 24 | | PK | | 8-0 | 21-28-11 | D06658J | | 11 | | D13428 | | X2 | | 050-099 |
| 13A | 24 | | PK | | 9-0 | 21-28-11 | D13428 | | X2 | | D06658J | | 11 | | 150-199, 275-299 |
| 13B | 24 | | PK | | 5-0 | 21-28-11 | D06658J | | 8 | | D05692J | | 1 | | 050-099 |
| 13B | 24 | | PK | | 5-0 | 21-28-11 | D05692J | | 1 | | D06658J | | 8 | | 150-199, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 17

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1118 | 286T1118 | | | P37-R1A-INTEGRATION (continued) | | | | | | | | | | | | | |
| 13C | 24 | | PK | | 10-0 | 21-28-11 | D13430 | | X1 | | | | TB0314Z | 7 | BJ | | 050-099 |
| 13C | 24 | | PK | | 13-0 | 21-28-11 | TB0314Z | | 7 | BJ | | | D13430 | X1 | | | 150-199, 275-299 |
| 13D | 22 | | PQ | K | 10-0 | 21-28-11 | D05692J | | 19 | | | | TB0314X | B009 | BJ | | 050-099 |
| 13D | 22 | | PA | | 13-0 | 21-28-11 | TB0314X | | B009 | BJ | | | D05692J | 19 | | | 150-199, 275-276 |
| 13DZ | | | | K | 0-0 | 21-28-11 | D05692J | | DED | | | | TB0314X | DED | | | 050-099 |
| 13F | 22 | | PA | | 11-0 | 21-26-31 | TB0314Z | | 7 | BJ | | | TB0320D | A003 | 2 | | 050-099 |
| 13F | 22 | | PA | | 11-0 | 21-26-31 | TB0320D | | A003 | 2 | | | TB0314Z | 7 | BJ | | 155-199, 276-299 |
| 143 | 22 | | PA | | 7-0 | 30-71-21 | D05962J | | 4 | | | | TB0190F | A017 | 2 | | 275 |
| 144 | 22 | | PA | | 7-0 | 30-71-22 | D05962J | | 1 | | | | TB0190X | D014 | BJ | | 275 |
| 145 | 20 | | PA | | 7-0 | 30-71-22 | D05962J | | 5 | | | | TB0190X | C018 | BJ | | 275 |
| 146 | 20 | | PA | | 7-0 | 30-71-22 | D05962J | | 6 | | | | TB0190X | C019 | BJ | | 275 |
| 147 | 22 | | PA | | 7-0 | 30-71-22 | D05962J | | 8 | | | | TB0190X | B013 | BJ | | 275 |
| 148 | 20 | | PA | | 6-0 | 30-71-23 | D05962J | | 2 | | | | TB0212X | A001 | BJ | | 275 |
| 149 | 20 | | PA | | 6-0 | 30-71-23 | D05962J | | 3 | | | | TB0212X | B001 | BJ | | 275 |
| 14A | 24 | | PK | | 10-0 | 28-22-12 | D06658J | | 13 | | | | TB0212Y | A007 | BJ | | 050-099, 275-299 |
| 150 | 20 | | PA | | 8-0 | 38-32-11 | D05760J | | 6 | | | | TB0210X | D020 | BJ | | 050-099, 155-199, 277-299 |
| 150 | 20 | | PA | | 8-0 | SPARE | D05760J | | 6 | | | | TB0210X | D020 | BJ | | 276 |
| 151 | 24 | | PK | | 4-0 | 21-51-21 | D04922J | | 6 | | | | TB0304X | C010 | BJ | | 150-199, 275-299 |
| 155 | 20 | | PA | | 7-0 | 30-71-11 | D05692J | | 11 | | | | TB0192G | 20 | 2 | | ALL |
| 156 | 22 | | PA | | 7-0 | 21-26-21 | D04922J | | 23 | | | | TB0192X | C005 | BJ | | ALL |
| 157 | 24 | | PK | | 6-0 | 21-26-21 | TB0192X | | C018 | BJ | | | D00976 | X2 | | | 050-099, 155-199, 276-299 |
| 157 | 24 | | PK | | 6-0 | 21-26-21 | D04922J | | 11 | | | | D00976 | X2 | | | 150-154, 275 |
| 158 | 24 | | PK | | 7-0 | 21-43-11 | D03680 | | A2 | | | | D04296J | 10 | | | 050-099 |
| 158 | 24 | | PK | | 6-0 | 21-43-11 | D03680 | | A2 | | | | D04296J | 10 | | | 150-199 |
| 158 | 24 | | PK | | 5-0 | 21-43-11 | D03680 | | A2 | | | | D04296J | 10 | | | 275-299 |
| 165 | 24 | | PK | | 4-0 | 21-44-11 | D04296J | | 16 | | | | TB0304Y | C011 | BJ | | ALL |
| 166 | 24 | | PK | | 4-0 | 21-44-11 | D04924J | | 13 | | | | TB0304Y | C011 | BJ | | ALL |
| 167 | 24 | | PK | | 7-0 | 27-81-11 | D02282 | | D1 | | | | TB0210Y | C001 | BJ | | ALL |
| 168 | 20 | | PA | | 3-0 | 27-81-11 | D02282 | | D2 | | | | GDX0001 | D.. | 2 | | ALL |
| 169 | 20 | | PA | | 2-0 | 27-81-21 | K00223 | | D2 | C | | | GDX0009 | A.. | 2 | | ALL |
| 170 | 24 | | PK | | 4-0 | 21-53-21 | TB0304X | | C002 | BJ | | | D04924J | 5 | | | ALL |
| 171 | 24 | | PK | | 4-0 | 21-53-21 | TB0304X | | D002 | BJ | | | D04924J | 6 | | | ALL |
| 172 | 24 | | PK | | 4-0 | 21-53-21 | TB0304X | | A003 | BJ | | | D04924J | 1 | | | ALL |
| 173 | 24 | | PK | | 4-0 | 21-53-21 | TB0304X | | B003 | BJ | | | D04924J | 2 | | | ALL |
| 174 | 24 | | PK | | 4-0 | 21-53-21 | TB0304X | | C003 | BJ | | | D04924J | 3 | | | ALL |
| 175 | 24 | | PK | | 4-0 | 21-53-21 | TB0304X | | D003 | BJ | | | D04924J | 4 | | | ALL |
| 178 | 16 | | PA | | 7-0 | 30-71-24 | D05692J | | 21 | | | | TB0210G | 6 | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 18

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1118 | 286T1118 | | | P37-R1A-INTEGRATION (continued) | | | | | | | | | | | | | |
| 178 | 16 | | PA | | 6-0 | 30-71-24 | D05692J | | 21 | | | | TB0210G | 6 | 2 | | 150-199 |
| 179 | 22 | | PA | | 6-0 | 27-81-21 | K00223 | | D1 | | C | | TB0210Y | C001 | BJ | | ALL |
| 180 | 16 | | PA | | 11-0 | 28-22-11 | D04922J | | 20 | | | | K00189 | A1 | D | | ALL |
| 181 | 16 | | PA | | 11-0 | 28-22-11 | D04922J | | 22 | | | | K00189 | B1 | D | | ALL |
| 182 | 16 | | PA | | 11-0 | 28-22-11 | D04922J | | 24 | | | | K00189 | C1 | D | | ALL |
| 183 | 12 | | PA | | 11-0 | 28-22-12 | D04924J | | 14 | | | | K00330 | A1 | D | | ALL |
| 184 | 12 | | PA | | 11-0 | 28-22-12 | D04924J | | 16 | | | | K00330 | B1 | D | | ALL |
| 185 | 12 | | PA | | 11-0 | 28-22-12 | D04924J | | 18 | | | | K00330 | C1 | D | | ALL |
| 188 | 20 | | PA | | 6-0 | 30-71-23 | D05962J | | 7 | | | | TB0212X | C001 | BJ | | 275 |
| 189 | 20 | | PA | | 7-0 | 30-71-24 | D05692J | | 25 | | | | TB0210Y | A001 | BJ | | 050-099 |
| 201B | 24 | | PW | B | 6-0 | 21-31-21 | D04296J | | 24 | | | | D05692J | 5 | | | ALL |
| 201R | 24 | | PW | B | 0-0 | 21-31-21 | D04296J | | 25 | | | | D05692J | 6 | | | ALL |
| 201Z | | | | B | 0-0 | 21-31-21 | D04296J | | 26 | | | | D05692J | 4 | | | ALL |
| 202B | 12 | | PB | D | 5-0 | 30-41-12 | D04296J | | 56 | | | | TB5078 | 1 | C | | ALL |
| 202R | 12 | | PB | D | 0-0 | 30-41-12 | D04296J | | 40 | | | | TB5078 | 2 | C | | ALL |
| 203B | 24 | | PW | A | 4-0 | 21-51-21 | D04922J | | 12 | | | | TB0304X | A010 | BJ | | ALL |
| 203R | 24 | | PW | A | 0-0 | 21-51-21 | D04922J | | 13 | | | | TB0304X | B010 | BJ | | ALL |
| 203Z | | | | A | 0-0 | 21-51-21 | D04922J | | DED | | | | TB0304X | DED | | | ALL |
| 204B | 20 | | PB | C | 6-0 | 21-31-21 | D04296J | | 21 | | | | D05692J | 8 | | | ALL |
| 204R | 20 | | PB | C | 0-0 | 21-31-21 | D04296J | | 22 | | | | D05692J | 9 | | | ALL |
| 500 | 24 | | PK | | 9-0 | 21-26-31 | D13806 | | X2 | | | | D06658J | 23 | | | ALL |
| 511 | 20 | | PA | | 7-0 | 25-33-11 | D10520 | | B3 | | | | TB0192X | D008 | BJ | | 050-099 |
| 511 | 20 | | PA | | 7-0 | 25-33-11 | D11394 | | B3 | | | | TB0192X | D008 | BJ | | 155-199 |
| 511 | 20 | | PA | | 6-0 | 25-33-11 | D13940 | | B3 | | | | TB0192X | D008 | BJ | | 277-299 |
| 514 | 22 | | PA | | 8-0 | 27-81-11 | D02282 | | D3 | | | | TB0212Y | C009 | BJ | | ALL |
| 515 | 22 | | PA | | 6-0 | 27-81-21 | K00223 | | D3 | | C | | TB0212Y | C009 | BJ | | ALL |
| 516 | 20 | | PA | | 8-0 | 25-33-11 | TB0254Y | | A006 | | BJ | | D04924J | 15 | | | 150-154 |
| 516 | 20 | | PA | | 8-0 | 25-33-11 | D04924J | | 15 | | | | TB0254Y | A006 | BJ | | 275-276 |
| 517 | 20 | | PA | | 6-0 | 25-33-11 | D10520 | | X1 | | | | TB0212Y | C005 | BJ | | 050-099 |
| 517 | 20 | | PA | | 4-0 | 21-58-16 | TB0254G | | 16 | | BJ | | D10520 | X1 | | | 150-152 |
| 517 | 20 | | PA | | 4-0 | 25-33-11 | TB0254Z | | 16 | | BJ | | D10520 | X1 | | | 153-154 |
| 517 | 20 | | PA | | 4-0 | 21-58-16 | TB0254Y | | A006 | | BJ | | D10520 | X1 | | | 275-276 |
| 518 | 20 | | PA | | 4-0 | 21-58-16 | TB0254Y | | A006 | | BJ | | D10520 | A2 | | | 150-152, 275-276 |
| 518 | 20 | | PA | | 4-0 | 25-33-11 | TB0254Y | | A006 | | BJ | | D10520 | A2 | | | 153-154 |
| 520 | 22 | | PA | | 3-0 | 25-33-11 | D10520 | | X2 | | | | TB0088D | A004 | 2 | | 050-099 |
| 520 | 22 | | PA | | 4-0 | 21-58-16 | D10520 | | X2 | | | | TB0088D | A004 | 2 | | 150-152, 275-276 |
| 520 | 22 | | PA | | 4-0 | 25-33-11 | D10520 | | X2 | | | | TB0088D | A004 | 2 | | 153-154 |
| 521 | 22 | | PA | | 4-0 | 21-58-16 | D10520 | | C2 | | | | TB0088D | A005 | 2 | | 150-152, 275-276 |
| 521 | 22 | | PA | | 4-0 | 25-33-11 | D10520 | | C2 | | | | TB0088D | A005 | 2 | | 153-154 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 19

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1118 | 286T1118 | | | P37-R1A-INTEGRATION (continued) | | | | | | | | | | | | | |
| 522 | 20 | | PA | 3-0 | 21-58-16 | D10520 | | C1 | | | | | GDX0002 | D.. | 2 | | 150-152, 275-276 |
| 522 | 20 | | PA | 3-0 | 25-33-12 | D10520 | | C1 | | | | | GDX0002 | D.. | 2 | | 153-154 |
| 523 | 22 | | PA | 2-0 | 25-33-11 | TB0088D | | A004 | 2 | * | | | TB0088D | A005 | 2 | | 050-099 |
| 523 | 22 | | PA | 2-0 | 21-58-16 | TB0088D | | A005 | 2 | | | | TB0088D | A004 | 2 | | 150-152, 275-276 |
| 523 | 22 | | PA | 2-0 | 25-33-11 | TB0088D | | A005 | 2 | | | | TB0088D | A004 | 2 | | 153-154, 162-164 |
| 523 | 22 | | PA | 2-0 | 25-33-11 | TB0088D | | A005 | 2 | | | | TB0088D | A004 | 2 | * | 155-157, 165-199, 277-299 |
| 524 | 22 | | PA | 8-0 | 25-33-11 | TB0088D | | C004 | 2 | | | | TB0210X | A019 | BJ | | 050-099, 153-199, 277-299 |
| 524 | 22 | | PA | 8-0 | 21-58-16 | TB0088D | | C004 | 2 | | | | TB0210X | A019 | BJ | | 150-152, 275-276 |
| 525 | 22 | | PA | 2-0 | 25-33-11 | TB0088D | | A003 | 2 | | | | TB0088D | A004 | 2 | * | 050-099, 155-157, 165-199, 277-299 |
| 525 | 22 | | PA | 2-0 | 25-33-11 | TB0088D | | A003 | 2 | | | | TB0088D | A004 | 2 | | 162-164 |
| 530 | 20 | | PA | 8-0 | 25-33-11 | D10520 | | A3 | | | | | D04924J | 17 | | | 150-154 |
| 530 | 20 | | PA | 2-0 | 25-33-11 | D10520 | | A3 | | | | | TB0254Y | C006 | BJ | | 275-276 |
| 537 | 20 | | PA | 8-0 | 25-33-11 | D04924J | | 17 | | | | | TB0254Y | C006 | BJ | | 275-276 |
| 538 | 22 | | PA | 9-0 | 21-26-31 | D13806 | | X1 | | | | | D06658J | 24 | | | ALL |
| 539 | 22 | | PA | 11-0 | 21-26-31 | D13806 | | A2 | | | | | TB0304Y | C024 | BJ | | 050-099 |
| 539 | 22 | | PA | 10-0 | 21-26-31 | D13806 | | A2 | | | | | TB0304Y | C024 | BJ | | 150-199 |
| 539 | 22 | | PA | 10-0 | 21-26-31 | D13806 | | A2 | | | | | TB0304X | B002 | BJ | | 275-299 |
| 540 | 24 | | PK | 8-0 | 21-43-11 | D03680 | | X1 | | | | | TB0320D | A004 | 2 | | 050-099, 155-199, 276-299 |
| 540 | 24 | | PK | 4-0 | 21-43-11 | D03680 | | X1 | | | | | TB0254Y | A010 | BJ | | 150-154, 275 |
| 541 | 24 | | PK | 4-0 | 21-43-11 | D04296J | | 8 | | | | | TB0320D | C004 | 2 | | 050-099, 155-199, 276-299 |
| 541 | 24 | | PK | 9-0 | 21-43-11 | D04296J | | 8 | | | | | TB0254Y | A010 | BJ | | 150-154, 275 |
| 545 | 24 | | PK | 8-0 | 21-44-21 | D04296J | | 18 | | | | | TB0274Y | C010 | BJ | | 050-099, 275-299 |
| 545 | 24 | | PK | 7-0 | 21-44-21 | D04296J | | 18 | | | | | TB0274Y | C010 | BJ | | 150-199 |
| 546 | 24 | | PK | 11-0 | 21-43-11 | D13806 | | B3 | | | | | TB0320D | A004 | 2 | | 050-099, 155-199, 276-299 |
| 546 | 24 | | PK | 10-0 | 21-43-11 | D13806 | | B3 | | | | | TB0254Y | A010 | BJ | | 150-154, 275 |
| 547 | 22 | | PA | 11-0 | 21-26-31 | D13806 | | A3 | | | | | TB0314Z | 7 | BJ | | 050-099 |
| 547 | 22 | | PA | 3-0 | 21-26-31 | D13806 | | A3 | | | | | TB0314Z | 7 | BJ | | 150-199, 275-299 |
| 550 | 24 | | PK | 5-0 | 21-43-11 | D04924J | | 23 | | | | | D06658J | 22 | | | ALL |
| 551 | 12 | | PA | 9-0 | 28-31-21 | C00376 | | A2 | D | | | | K02094 | A2 | D | | 050-099 |
| 551 | 12 | | PA | 10-0 | 28-31-21 | C00376 | | A2 | D | | | | D05760J | 8 | | | 155-157, 165-199, 277-299 |
| 551 | 12 | | PA | 7-0 | 28-31-21 | C00376 | | A2 | D | | | | K02094 | A2 | D | | 162-164, 276 |
| 552 | 12 | | PA | 9-0 | 28-31-21 | C00376 | | B2 | D | | | | K02094 | B2 | D | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 20

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|---------|-------|------|------|---------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1118 | 286T1118 | | | P37-R1A-INTEGRATION (continued) | | | | | | | | | | | |
| 552 | 12 | | PA | 10-0 | 28-31-21 | C00376 | B2 | D | | D05760J | 7 | | | 155-157, 165-199, 277-299 | |
| 552 | 12 | | PA | 7-0 | 28-31-21 | C00376 | B2 | D | | K02094 | B2 | D | | 162-164, 276 | |
| 553 | 12 | | PA | 9-0 | 28-31-21 | C00376 | C2 | D | | K02094 | C2 | D | | 050-099 | |
| 553 | 12 | | PA | 10-0 | 28-31-21 | C00376 | C2 | D | | D05760J | 5 | | | 155-157, 165-199, 277-299 | |
| 553 | 12 | | PA | 7-0 | 28-31-21 | C00376 | C2 | D | | K02094 | C2 | D | | 162-164, 276 | |
| 554 | 12 | | PA | 7-0 | 28-31-21 | D05760J | | 8 | | K02094 | A1 | D | | 050-099 | |
| 554 | 12 | | PA | 6-0 | 28-31-21 | D05760J | | 8 | | K02094 | A1 | D | | 162-164, 276 | |
| 555 | 12 | | PA | 7-0 | 28-31-21 | D05760J | | 7 | | K02094 | B1 | D | | 050-099 | |
| 555 | 12 | | PA | 6-0 | 28-31-21 | D05760J | | 7 | | K02094 | B1 | D | | 162-164, 276 | |
| 556 | 12 | | PA | 7-0 | 28-31-21 | D05760J | | 5 | | K02094 | C1 | D | | 050-099 | |
| 556 | 12 | | PA | 6-0 | 28-31-21 | D05760J | | 5 | | K02094 | C1 | D | | 162-164, 276 | |
| 557 | 20 | | PA | 4-0 | 25-31-12 | D10520 | B3 | | | TB0254F | C017 | BJ | | 150-152 | |
| 557 | 20 | | PA | 3-0 | 25-33-11 | D10520 | B3 | | | D11394 | A2 | | | 153-154 | |
| 558 | 20 | | PA | 4-0 | 25-31-12 | D10520 | D3 | | | TB0254F | A017 | BJ | | 150-152 | |
| 558 | 20 | | PA | 7-0 | 25-31-12 | D10520 | D3 | | | TB0192X | C019 | BJ | | 153-154 | |
| 559 | 20 | | PA | 4-0 | 25-31-12 | D10520 | B2 | | | TB0254G | 16 | BJ | | 150-152 | |
| 559 | 20 | | PA | 4-0 | 25-33-11 | D10520 | B2 | | | TB0254Z | 16 | BJ | | 153-154 | |
| 560 | 20 | | PA | 4-0 | 25-31-12 | D10520 | D2 | | | TB0254G | 16 | BJ | | 150-152 | |
| 560 | 20 | | PA | 4-0 | 25-31-12 | D10520 | D2 | | | TB0254Z | 16 | BJ | | 153-154 | |
| 561 | 20 | | PA | 3-0 | 25-33-11 | D10520 | B2 | | | TB0254Y | A006 | BJ | | 050-099 | |
| 561 | 20 | | PA | 4-0 | 25-33-11 | D11394 | B2 | | | TB0254Y | A006 | BJ | | 155-199 | |
| 561 | 20 | | PA | 4-0 | 25-33-11 | D13940 | B2 | | | TB0254Y | A006 | BJ | | 277-299 | |
| 562 | 20 | | PA | 3-0 | 25-33-11 | D10520 | D2 | | | TB0254Y | A006 | BJ | | 050-099 | |
| 562 | 20 | | PA | 7-0 | SPARE | D13940 | D2 | | | TB0320X | C006 | BJ | | 280-299 | |
| 563 | 20 | | PA | 3-0 | 25-33-11 | D10520 | D3 | | | TB0254Y | C006 | BJ | | 050-099 | |
| 563 | 20 | | PA | 7-0 | SPARE | D13940 | D3 | | | TB0320X | D006 | BJ | | 280-299 | |
| 689 | 16 | | PA | 7-0 | 30-71-24 | D05692J | | 23 | | TB0210G | 6 | 2 | | 050-099, 150-199 | |
| 70A | 22 | | PQ | G | 11-0 | 21-28-11 | D13428 | A2 | | TB0314X | C009 | BJ | | 050-099 | |
| 70A | 22 | | PA | G | 13-0 | 21-28-11 | D13428 | A2 | | TB0314X | C009 | BJ | | 150-199, 275-299 | |
| 70AZ | | | | G | 0-0 | 21-28-11 | D13428 | DED | | TB0314X | DED | | | 050-099 | |
| 70B | 24 | | PK | | 7-0 | 21-26-21 | D04922J | 11 | | TB0190X | A003 | BJ | | 050-099, 155-199, 276-299 | |
| A-A | | | | | 0-0 | 21-26-31 | TS0493 | 1 | | TS0493 | CAP | Y | | 050-099, 277-299 | |
| A-A | | | | | 0-0 | 21-26-31 | TS0493 | 1 | | SP03678 | CAP | Y | | 150-199, 275-276 | |
| A-C | | | | | 0-0 | 21-26-31 | TS0493 | 2 | | SP03680 | | W | | ALL | |
| A-E | | | | | 0-0 | 21-26-31 | TS0494 | 1 | | SP03682 | | W | | ALL | |
| A-F | | | | | 0-0 | 21-26-31 | TS0494 | 2 | | SP03684 | | W | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 21

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1118 | 286T1118 | | | P37-R1A-INTEGRATION (continued) | | | | | | | | | | | | |
| PA1 | | | | 0-0 | 99-99-99 | D02278 | | G2 | | | D02278 | | G3 | | ALL | |
| PB1 | | | | 0-0 | 99-99-99 | D02280 | | G2 | | | D02280 | | G3 | | ALL | |
| PC1 | | | | 0-0 | 99-99-99 | D02282 | | G2 | | | D02282 | | G3 | | ALL | |
| W1119 | 286T1119 | | | E1-5 SHELF EF1S SG,R | | | | | | | | | | | | |
| 001 | 24 | | PK | 6-0 | 34-22-24 | D05081P | | 25 | | | TB0119G | 82 | 2 | | 050-099, 280-299 | |
| 001 | 24 | | PK | 5-3 | 34-22-24 | D05081P | | 25 | | | TB0119G | 82 | 2 | | 150-199, 275-278 | |
| 002 | 24 | | PK | 7-0 | 34-22-24 | D05081P | | 27 | | | TB0119G | 83 | 2 | | 050-099, 280-299 | |
| 002 | 24 | | PK | 6-4 | 34-22-24 | D05081P | | 27 | | | TB0119G | 83 | 2 | | 150-199, 275-278 | |
| 003 | 24 | | PK | 7-0 | 34-22-24 | D05081P | | 28 | | | TB0119G | 84 | 2 | | 050-099, 280-299 | |
| 003 | 24 | | PK | 6-4 | 34-22-24 | D05081P | | 28 | | | TB0119G | 84 | 2 | | 150-199, 275-278 | |
| 005 | 24 | | PK | 7-0 | 34-22-25 | D05085P | | 25 | | | TB0119G | 85 | 2 | | 050-099, 280-299 | |
| 005 | 24 | | PK | 6-3 | 34-22-25 | D05085P | | 25 | | | TB0119G | 85 | 2 | | 150-199, 275-278 | |
| 006 | 24 | | PK | 7-0 | 34-22-25 | D05085P | | 27 | | | TB0119G | 86 | 2 | | 050-099, 280-299 | |
| 006 | 24 | | PK | 6-3 | 34-22-25 | D05085P | | 27 | | | TB0119G | 86 | 2 | | 150-199, 275-278 | |
| 007 | 24 | | PK | 7-0 | 34-22-25 | D05085P | | 28 | | | TB0119G | 89 | 2 | | 050-099, 280-299 | |
| 007 | 24 | | PK | 6-3 | 34-22-25 | D05085P | | 28 | | | TB0119G | 89 | 2 | | 150-199, 275-278 | |
| 008 | 24 | | PK | 5-0 | 34-22-27 | D00373D | | E11 | | | TB0119G | 26 | 2 | | 050-099, 280-299 | |
| 008 | 24 | | PK | 3-4 | 34-22-27 | D00373D | | E11 | | | TB0119G | 26 | 2 | | 150-199, 275-278 | |
| 009 | 24 | | PK | 4-0 | 34-22-27 | D00373D | | G11 | | | TB0119H | 24 | 2 | | 050-099, 280-299 | |
| 009 | 24 | | PK | 3-1 | 34-22-27 | D00373D | | G11 | | | TB0119H | 24 | 2 | | 150-199, 275-278 | |
| 010 | 24 | | PK | 4-0 | 34-22-27 | D00373D | | J12 | | | TB0119G | 22 | 2 | | 050-099, 280-299 | |
| 010 | 24 | | PK | 3-1 | 34-22-27 | D00373D | | J12 | | | TB0119G | 22 | 2 | | 150-199, 275-278 | |
| 011 | 24 | | PK | 4-0 | 34-22-27 | D00373D | | K12 | | | TB0119G | 23 | 2 | | 050-099, 280-299 | |
| 011 | 24 | | PK | 3-1 | 34-22-27 | D00373D | | K12 | | | TB0119G | 23 | 2 | | 150-199, 275-278 | |
| 012 | 24 | | PV | AL | 6-0 | 34-22-26 | D00373C | | 1 | | TB0119F | A071 | 2 | | 050-099, 280-299 | |
| 012 | 24 | | PV | AL | 4-5 | 34-22-26 | D00373C | | 1 | | TB0119F | A071 | 2 | | 150-199, 275-278 | |
| 012Z | | | | AL | 0-0 | 34-22-26 | D00373C | | DED | | TB0119F | DED | | | ALL | |
| 013 | 20 | | PA | | 3-0 | 34-22-26 | D00373C | | 4 | | GDX0001 | A.. | 2 | | 050-099, 280-299 | |
| 013 | 20 | | PA | | 1-6 | 34-22-26 | D00373C | | 4 | | GDX0001 | A.. | 2 | | 150-199, 275-278 | |
| 014 | 20 | | PA | | 3-0 | 34-22-26 | D00373C | | 6 | | GDX0001 | D.. | 2 | | 050-099, 280-299 | |
| 014 | 20 | | PA | | 1-6 | 34-22-26 | D00373C | | 6 | | GDX0001 | D.. | 2 | | 150-199, 275-278 | |
| 015 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | F08 | | GDX0001 | D.. | 2 | | 050-099, 280-299 | |
| 015 | 22 | | PA | | 1-6 | 34-22-26 | D00373B | | F08 | | GDX0001 | D.. | 2 | | 150-199, 275-278 | |
| 016 | 22 | | PA | | 4-0 | 34-31-21 | D00373A | | E12 | | TB0119F | A021 | 2 | | 050-099, 280-299 | |
| 016 | 22 | | PA | | 3-1 | 34-31-21 | D00373A | | E12 | | TB0119F | A021 | 2 | | 150-199, 275-278 | |
| 017 | 22 | | PA | | 4-0 | 34-22-23 | D00373D | | F13 | | TB0119F | C021 | 2 | | ALL | |
| 018 | 24 | | PK | | 3-0 | 33-16-14 | D00373D | | B12 | | TB0119F | C112 | 2 | | 050-099, 280-299 | |
| 018 | 24 | | PK | | 2-2 | 33-16-14 | D00373D | | B12 | | TB0119F | C112 | 2 | | 150-199, 275-278 | |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 22

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1119 | 286T1119 | | | E1-5 SHELF EF1S SG,R (continued) | | | | | | | | | | | |
| 019 | 22 | | PA | 3-0 | 34-22-27 | D00373D | J11 | | | | GDX0001 | D.. | 2 | | 050-099, 280-299 |
| 019 | 22 | | PA | 1-6 | 34-22-27 | D00373D | J11 | | | | GDX0001 | D.. | 2 | | 150-199, 275-278 |
| 020 | 22 | | PA | 3-0 | 34-22-27 | D00373D | A12 | | | | GDX0001 | D.. | 2 | | 050-099, 280-299 |
| 020 | 22 | | PA | 1-6 | 34-22-27 | D00373D | A12 | | | | GDX0001 | D.. | 2 | | 150-199, 275-278 |
| 022 | 22 | | PA | 3-0 | 34-22-27 | D00373D | C11 | | | | GDX0002 | D.. | 2 | | 050-099, 280-299 |
| 022 | 22 | | PA | 1-11 | 34-22-27 | D00373D | C11 | | | | GDX0002 | D.. | 2 | | 150-199, 275-278 |
| 023 | 22 | | PA | 3-0 | 34-22-27 | D00373A | G12 | | | | GDX0002 | D.. | 2 | | 050-099, 280-299 |
| 023 | 22 | | PA | 1-11 | 34-22-27 | D00373A | G12 | | | | GDX0002 | D.. | 2 | | 150-199, 275-278 |
| 024 | 24 | | PK | 6-0 | 34-22-24 | D00373D | A09 | | | | TB0119G | 82 | 2 | | 050-099, 280-299 |
| 024 | 24 | | PK | 4-8 | 34-22-24 | D00373D | A09 | | | | TB0119G | 82 | 2 | | 150-199, 275-278 |
| 025 | 24 | | PK | 7-0 | 34-22-24 | D00373D | B09 | | | | TB0119G | 83 | 2 | | 050-099, 280-299 |
| 025 | 24 | | PK | 5-3 | 34-22-24 | D00373D | B09 | | | | TB0119G | 83 | 2 | | 150-199, 275-278 |
| 026 | 24 | | PK | 7-0 | 34-22-24 | D00373D | C09 | | | | TB0119G | 84 | 2 | | 050-099, 280-299 |
| 026 | 24 | | PK | 5-3 | 34-22-24 | D00373D | C09 | | | | TB0119G | 84 | 2 | | 150-199, 275-278 |
| 027 | 24 | | PK | 7-0 | 34-22-24 | D00373A | C09 | | | | TB0119G | 84 | 2 | | 050-099, 280-299 |
| 027 | 24 | | PK | 5-3 | 34-22-24 | D00373A | C09 | | | | TB0119G | 84 | 2 | | 150-199, 275-278 |
| 028 | 24 | | PK | 7-0 | 34-22-24 | D00373A | B09 | | | | TB0119G | 83 | 2 | | 050-099, 280-299 |
| 028 | 24 | | PK | 5-3 | 34-22-24 | D00373A | B09 | | | | TB0119G | 83 | 2 | | 150-199, 275-278 |
| 029 | 24 | | PK | 6-0 | 34-22-24 | D00373A | A09 | | | | TB0119G | 82 | 2 | | 050-099, 280-299 |
| 029 | 24 | | PK | 4-8 | 34-22-24 | D00373A | A09 | | | | TB0119G | 82 | 2 | | 150-199, 275-278 |
| 030 | 24 | | PK | 7-0 | 34-22-24 | D00373A | F09 | | | | TB0119G | 85 | 2 | | 050-099, 280-299 |
| 030 | 24 | | PK | 5-3 | 34-22-24 | D00373A | F09 | | | | TB0119G | 85 | 2 | | 150-199, 275-278 |
| 031 | 24 | | PK | 7-0 | 34-22-24 | D00373A | G09 | | | | TB0119G | 86 | 2 | | 050-099, 280-299 |
| 031 | 24 | | PK | 5-3 | 34-22-24 | D00373A | G09 | | | | TB0119G | 86 | 2 | | 150-199, 275-278 |
| 032 | 24 | | PK | 7-0 | 34-22-24 | D00373A | H09 | | | | TB0119G | 89 | 2 | | 050-099, 280-299 |
| 032 | 24 | | PK | 5-3 | 34-22-24 | D00373A | H09 | | | | TB0119G | 89 | 2 | | 150-199, 275-278 |
| 033 | 24 | | PK | 7-0 | 34-22-25 | D00373D | F09 | | | | TB0119G | 85 | 2 | | 050-099, 280-299 |
| 033 | 24 | | PK | 5-3 | 34-22-25 | D00373D | F09 | | | | TB0119G | 85 | 2 | | 150-199, 275-278 |
| 034 | 24 | | PK | 7-0 | 34-22-25 | D00373D | G09 | | | | TB0119G | 86 | 2 | | 050-099, 280-299 |
| 034 | 24 | | PK | 5-3 | 34-22-25 | D00373D | G09 | | | | TB0119G | 86 | 2 | | 150-199, 275-278 |
| 035 | 24 | | PK | 7-0 | 34-22-25 | D00373D | H09 | | | | TB0119G | 89 | 2 | | 050-099, 280-299 |
| 035 | 24 | | PK | 5-3 | 34-22-25 | D00373D | H09 | | | | TB0119G | 89 | 2 | | 150-199, 275-278 |
| 036 | 22 | | PA | 5-0 | 34-22-13 | D05647P | 10 | | | | TB0119G | 125 | 2 | | ALL |
| 041 | 20 | | PA | 2-0 | 34-22-26 | D00373B | REF | | Y | | GDX0003 | S.. | 2 | | 162-199 |
| 042 | 20 | | PA | 2-0 | 34-22-26 | D00373B | REF | | Y | | GDX0003 | S.. | 2 | | 162-199 |
| 043 | 22 | | PA | 2-2 | 34-45-14 | D00373E | G11 | | | | TB0119Y | A102 | BJ | | 157, 167-199, 277-278 |
| 043 | 22 | | PA | 3-0 | 34-45-14 | D00373E | G11 | | | | TB0119Y | A102 | BJ | | 280-299 |
| 056 | 22 | | PA | 3-0 | 34-22-26 | D00373B | E10 | | | | GDX0003 | S.. | 2 | | 050-099, 280-299 |
| 056 | 22 | | PA | 2-0 | 34-22-26 | D00373B | E10 | | | | GDX0003 | S.. | 2 | | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 23

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1119 | 286T1119 | | | E1-5 SHELF EF1S SG,R (continued) | | | | | | | | | | | | | |
| 073 | 24 | | PK | | 3-0 | 34-22-27 | D00373A | | F12 | | | | TB0119G | 105 | 2 | | ALL |
| 074 | 22 | | PQ | CX | 3-0 | 34-22-26 | D00373F | | 1 | | | | TB0119F | A111 | 2 | | ALL |
| 074Z | | | | CX | 0-0 | 34-22-26 | D00373F | | DED | | | | TB0119F | DED | | | ALL |
| 075 | 22 | | PA | | 5-0 | 34-22-26 | D00373F | | 4 | | | | TB0119G | 125 | 2 | | ALL |
| 091 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | F09 | | | | GDX0003 | S.. | 2 | | ALL |
| 092 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | G09 | | | | GDX0003 | S.. | 2 | | 050-099, 280-299 |
| 092 | 22 | | PA | | 2-0 | 34-22-26 | D00373B | | G09 | | | | GDX0003 | S.. | 2 | | 150-199, 275-278 |
| 094 | 22 | | PA | | 5-0 | 34-22-26 | D00373B | | D08 | | | | TB0119G | 142 | 2 | | 050-099, 280-299 |
| 094 | 22 | | PA | | 3-7 | 34-22-26 | D00373B | | D08 | | | | TB0119G | 142 | 2 | | 150-199, 275-278 |
| 097 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | D10 | | | | GDX0003 | S.. | 2 | | 050-099, 280-299 |
| 097 | 22 | | PA | | 2-0 | 34-22-26 | D00373B | | D10 | | | | GDX0003 | S.. | 2 | | 150-199, 275-278 |
| 098 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | D12 | | | | GDX0003 | S.. | 2 | | 050-099, 280-299 |
| 098 | 22 | | PA | | 2-0 | 34-22-26 | D00373B | | D12 | | | | GDX0003 | S.. | 2 | | 150-199, 275-278 |
| 101 | 24 | | PK | | 4-0 | 34-46-12 | D00373E | | A11 | | | | TB0119D | C016 | 2 | | 050-099 |
| 101 | 24 | | PK | | 2-6 | 34-46-12 | D00373E | | A11 | | | | TB0119D | C016 | 2 | | 150-199, 275-278 |
| 102 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | D11 | | | | GDX0001 | S.. | 2 | | 050-099, 280-299 |
| 102 | 22 | | PA | | 1-6 | 34-22-26 | D00373B | | D11 | | | | GDX0001 | S.. | 2 | | 150-199, 275-278 |
| 104 | 24 | | PK | | 5-0 | 34-22-27 | D00373D | | A11 | | | | TB0119G | 138 | 2 | | 050-099, 280-299 |
| 104 | 24 | | PK | | 3-6 | 34-22-27 | D00373D | | A11 | | | | TB0119G | 138 | 2 | | 150-199, 275-278 |
| 105 | 22 | | PA | | 3-0 | 34-22-27 | D00373D | | J13 | | | | GDX0001 | D.. | 2 | | 050-099, 280-299 |
| 105 | 22 | | PA | | 1-6 | 34-22-27 | D00373D | | J13 | | | | GDX0001 | D.. | 2 | | 150-199, 275-278 |
| 106 | 22 | | PA | | 3-0 | 34-22-26 | D00373D | | D12 | | | | GDX0001 | S.. | 2 | | 050-099, 280-299 |
| 106 | 22 | | PA | | 1-6 | 34-22-26 | D00373D | | D12 | | | | GDX0001 | S.. | 2 | | 150-199, 275-278 |
| 107 | 24 | | PK | | 5-0 | 34-22-26 | D00373A | | K13 | | | | TB0119H | 139 | 2 | | 050-099, 280-299 |
| 107 | 24 | | PK | | 3-6 | 34-22-26 | D00373A | | K13 | | | | TB0119H | 139 | 2 | | 150-199, 275-278 |
| 109 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | D05 | | | | GDX0003 | S.. | 2 | | 050-099, 280-299 |
| 109 | 22 | | PA | | 2-0 | 34-22-26 | D00373B | | D05 | | | | GDX0003 | S.. | 2 | | 150-199, 275-278 |
| 112 | 24 | | PK | | 5-0 | 34-22-26 | D00373A | | C14 | | | | TB0119H | 139 | 2 | | 050-099, 280-299 |
| 112 | 24 | | PK | | 3-6 | 34-22-26 | D00373A | | C14 | | | | TB0119H | 139 | 2 | | 150-199, 275-278 |
| 115 | 22 | | PA | | 1-6 | 34-22-26 | D00373B | | K04 | | | | GDX0001 | S.. | 2 | | 156-157, 166-199, 277-278 |
| 115 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | K04 | | | | GDX0001 | S.. | 2 | | 280-299 |
| 123 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | F06 | | | | GDX0003 | S.. | 2 | | 050-099, 280-299 |
| 123 | 22 | | PA | | 2-0 | 34-22-26 | D00373B | | F06 | | | | GDX0003 | S.. | 2 | | 150-199, 275-278 |
| 125 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | B04 | | | | GDX0003 | S.. | 2 | | 050-099, 280-299 |
| 125 | 22 | | PA | | 2-0 | 34-22-26 | D00373B | | B04 | | | | GDX0003 | S.. | 2 | | 150-199, 275-278 |
| 126 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | G06 | | | | GDX0003 | S.. | 2 | | 050-099, 280-299 |
| 126 | 22 | | PA | | 2-0 | 34-22-26 | D00373B | | G06 | | | | GDX0003 | S.. | 2 | | 150-199, 275-278 |
| 128 | 22 | | PA | | 3-0 | 34-22-26 | D00373A | | D14 | | | | TB0119G | 110 | 2 | | 050-099, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 24

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1119 | 286T1119 | | | E1-5 SHELF EF1S SG,R (continued) | | | | | | | | | | | |
| 128 | 22 | | PA | | 2-2 | 34-22-26 | D00373A | D14 | | | TB0119G | 110 | 2 | | 150-199, 275-278 |
| 136 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | J05 | | | GDZ0003 | S.. | 2 | | ALL |
| 201B | 24 | | PW | IA | 6-0 | 34-22-24 | TB0119H | 63 | 2 | | D00373D | F05 | | | 050-099, 280-299 |
| 201B | 24 | | PW | IA | 4-3 | 34-22-24 | TB0119H | 63 | 2 | | D00373D | F05 | | | 150-199, 275-278 |
| 201R | 24 | | PW | IA | 0-0 | 34-22-24 | TB0119H | 61 | 2 | | D00373D | E05 | | | ALL |
| 201Z | | | IA | | 0-0 | 34-22-24 | D00373D | DED | | | GDY0010 | S.. | 2 | | ALL |
| 202W | 26 | | BW | IB | 4-0 | 34-22-24 | D05081P | 2 | | | D00373E | B01 | | | 050-099, 280-299 |
| 202W | 26 | | BW | IB | 2-3 | 34-22-24 | D05081P | 2 | | | D00373E | B01 | | | 150-199, 275-278 |
| 202WN | 26 | | BW | IB | 0-0 | 34-22-24 | D05081P | 1 | | | D00373E | A01 | | | ALL |
| 202Z | | | IB | | 0-0 | 34-22-24 | D05081P | 19 | | | GDZ0002 | S.. | 2 | | ALL |
| 203W | 26 | | BW | IC | 4-0 | 34-22-24 | D05081P | 4 | | | D00373E | B02 | | | 050-099, 280-299 |
| 203W | 26 | | BW | IC | 2-3 | 34-22-24 | D05081P | 4 | | | D00373E | B02 | | | 150-199, 275-278 |
| 203WN | 26 | | BW | IC | 0-0 | 34-22-24 | D05081P | 3 | | | D00373E | A02 | | | ALL |
| 203Z | | | IC | | 0-0 | 34-22-24 | D05081P | 20 | | | GDZ0002 | S.. | 2 | | ALL |
| 204W | 26 | | BW | ID | 4-0 | 34-22-24 | D05081P | 6 | | | D00373E | B03 | | | 050-099, 280-299 |
| 204W | 26 | | BW | ID | 2-3 | 34-22-24 | D05081P | 6 | | | D00373E | B03 | | | 150-199, 275-278 |
| 204WN | 26 | | BW | ID | 0-0 | 34-22-24 | D05081P | 5 | | | D00373E | A03 | | | ALL |
| 204Z | | | ID | | 0-0 | 34-22-24 | D05081P | 21 | | | GDZ0002 | S.. | 2 | | ALL |
| 205W | 26 | | BW | IE | 4-0 | 34-22-24 | D05081P | 8 | | | D00373E | B04 | | | 050-099, 280-299 |
| 205W | 26 | | BW | IE | 2-3 | 34-22-24 | D05081P | 8 | | | D00373E | B04 | | | 150-199, 275-278 |
| 205WN | 26 | | BW | IE | 0-0 | 34-22-24 | D05081P | 7 | | | D00373E | A04 | | | ALL |
| 205Z | | | IE | | 0-0 | 34-22-24 | D05081P | 22 | | | GDZ0002 | S.. | 2 | | ALL |
| 206W | 26 | | BW | IF | 4-0 | 34-22-24 | D05081P | 10 | | | D00373E | B05 | | | 050-099, 280-299 |
| 206W | 26 | | BW | IF | 2-3 | 34-22-24 | D05081P | 10 | | | D00373E | B05 | | | 150-199, 275-278 |
| 206WN | 26 | | BW | IF | 0-0 | 34-22-24 | D05081P | 9 | | | D00373E | A05 | | | ALL |
| 206Z | | | IF | | 0-0 | 34-22-24 | D05081P | 23 | | | GDZ0002 | S.. | 2 | | ALL |
| 207W | 26 | | BW | IG | 4-0 | 34-22-24 | D05081P | 12 | | | D00373E | B06 | | | 050-099, 280-299 |
| 207W | 26 | | BW | IG | 2-3 | 34-22-24 | D05081P | 12 | | | D00373E | B06 | | | 150-199, 275-278 |
| 207WN | 26 | | BW | IG | 0-0 | 34-22-24 | D05081P | 11 | | | D00373E | A06 | | | ALL |
| 207Z | | | IG | | 0-0 | 34-22-24 | D05081P | 29 | | | GDZ0003 | S.. | 2 | | ALL |
| 208W | 26 | | BW | IH | 4-0 | 34-22-24 | D05081P | 14 | | | D00373E | B07 | | | 050-099, 280-299 |
| 208W | 26 | | BW | IH | 2-3 | 34-22-24 | D05081P | 14 | | | D00373E | B07 | | | 150-199, 275-278 |
| 208WN | 26 | | BW | IH | 0-0 | 34-22-24 | D05081P | 13 | | | D00373E | A07 | | | ALL |
| 208Z | | | IH | | 0-0 | 34-22-24 | D05081P | 30 | | | GDZ0003 | S.. | 2 | | ALL |
| 209W | 26 | | BW | II | 4-0 | 34-22-24 | D05081P | 16 | | | D00373E | B08 | | | 050-099, 280-299 |
| 209W | 26 | | BW | II | 2-3 | 34-22-24 | D05081P | 16 | | | D00373E | B08 | | | 150-199, 275-278 |
| 209WN | 26 | | BW | II | 0-0 | 34-22-24 | D05081P | 15 | | | D00373E | A08 | | | ALL |
| 209Z | | | II | | 0-0 | 34-22-24 | D05081P | 31 | | | GDZ0003 | S.. | 2 | | ALL |
| 210W | 26 | | BW | IJ | 4-0 | 34-22-24 | D05081P | 18 | | | D00373E | B09 | | | 050-099, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 25

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1119 | 286T1119 | | | E1-5 SHELF EF1S SG,R (continued) | | | | | | | | | | | | |
| 210W | 26 | BW | IJ | 2-3 | 34-22-24 | D05081P | 18 | | | | D00373E | B09 | | | 150-199, 275-278 | |
| 210WN | 26 | BW | IJ | 0-0 | 34-22-24 | D05081P | 17 | | | | D00373E | A09 | | | ALL | |
| 210Z | | | IJ | 0-0 | 34-22-24 | D05081P | 35 | | | | GDZ0003 | S.. | 2 | | ALL | |
| 211W | 26 | BW | IK | 4-0 | 34-22-25 | D05085P | 2 | | | | D00373E | D01 | | | 050-099, 280-299 | |
| 211W | 26 | BW | IK | 2-2 | 34-22-25 | D05085P | 2 | | | | D00373E | D01 | | | 150-199, 275-278 | |
| 211WN | 26 | BW | IK | 0-0 | 34-22-25 | D05085P | 1 | | | | D00373E | C01 | | | ALL | |
| 211Z | | | IK | 0-0 | 34-22-25 | D05085P | 19 | | | | GDZ0002 | S.. | 2 | | ALL | |
| 212W | 26 | BW | IL | 4-0 | 34-22-25 | D05085P | 4 | | | | D00373E | D02 | | | 050-099, 280-299 | |
| 212W | 26 | BW | IL | 2-2 | 34-22-25 | D05085P | 4 | | | | D00373E | D02 | | | 150-199, 275-278 | |
| 212WN | 26 | BW | IL | 0-0 | 34-22-25 | D05085P | 3 | | | | D00373E | C02 | | | ALL | |
| 212Z | | | IL | 0-0 | 34-22-25 | D05085P | 20 | | | | GDZ0002 | S.. | 2 | | ALL | |
| 213W | 26 | BW | IM | 4-0 | 34-22-25 | D05085P | 6 | | | | D00373E | D03 | | | 050-099, 280-299 | |
| 213W | 26 | BW | IM | 2-2 | 34-22-25 | D05085P | 6 | | | | D00373E | D03 | | | 150-199, 275-278 | |
| 213WN | 26 | BW | IM | 0-0 | 34-22-25 | D05085P | 5 | | | | D00373E | C03 | | | ALL | |
| 213Z | | | IM | 0-0 | 34-22-25 | D05085P | 21 | | | | GDZ0002 | S.. | 2 | | ALL | |
| 214W | 26 | BW | IN | 4-0 | 34-22-25 | D05085P | 8 | | | | D00373E | D04 | | | 050-099, 280-299 | |
| 214W | 26 | BW | IN | 2-2 | 34-22-25 | D05085P | 8 | | | | D00373E | D04 | | | 150-199, 275-278 | |
| 214WN | 26 | BW | IN | 0-0 | 34-22-25 | D05085P | 7 | | | | D00373E | C04 | | | ALL | |
| 214Z | | | IN | 0-0 | 34-22-25 | D05085P | 22 | | | | GDZ0002 | S.. | 2 | | ALL | |
| 215W | 26 | BW | IO | 4-0 | 34-22-25 | D05085P | 10 | | | | D00373E | D05 | | | 050-099, 280-299 | |
| 215W | 26 | BW | IO | 2-2 | 34-22-25 | D05085P | 10 | | | | D00373E | D05 | | | 150-199, 275-278 | |
| 215WN | 26 | BW | IO | 0-0 | 34-22-25 | D05085P | 9 | | | | D00373E | C05 | | | ALL | |
| 215Z | | | IO | 0-0 | 34-22-25 | D05085P | 23 | | | | GDZ0002 | S.. | 2 | | ALL | |
| 216W | 26 | BW | IP | 4-0 | 34-22-25 | D05085P | 12 | | | | D00373E | D06 | | | 050-099, 280-299 | |
| 216W | 26 | BW | IP | 2-2 | 34-22-25 | D05085P | 12 | | | | D00373E | D06 | | | 150-199, 275-278 | |
| 216WN | 26 | BW | IP | 0-0 | 34-22-25 | D05085P | 11 | | | | D00373E | C06 | | | ALL | |
| 216Z | | | IP | 0-0 | 34-22-25 | D05085P | 29 | | | | GDZ0002 | S.. | 2 | | ALL | |
| 217W | 26 | BW | IQ | 4-0 | 34-22-25 | D05085P | 14 | | | | D00373E | D07 | | | 050-099, 280-299 | |
| 217W | 26 | BW | IQ | 2-2 | 34-22-25 | D05085P | 14 | | | | D00373E | D07 | | | 150-199, 275-278 | |
| 217WN | 26 | BW | IQ | 0-0 | 34-22-25 | D05085P | 13 | | | | D00373E | C07 | | | ALL | |
| 217Z | | | IQ | 0-0 | 34-22-25 | D05085P | 30 | | | | GDZ0003 | S.. | 2 | | ALL | |
| 218W | 26 | BW | IR | 4-0 | 34-22-25 | D05085P | 16 | | | | D00373E | D08 | | | 050-099, 280-299 | |
| 218W | 26 | BW | IR | 2-2 | 34-22-25 | D05085P | 16 | | | | D00373E | D08 | | | 150-199, 275-278 | |
| 218WN | 26 | BW | IR | 0-0 | 34-22-25 | D05085P | 15 | | | | D00373E | C08 | | | ALL | |
| 218Z | | | IR | 0-0 | 34-22-25 | D05085P | 31 | | | | GDZ0003 | S.. | 2 | | ALL | |
| 219W | 26 | BW | IS | 4-0 | 34-22-25 | D05085P | 18 | | | | D00373E | D09 | | | 050-099, 280-299 | |
| 219W | 26 | BW | IS | 2-2 | 34-22-25 | D05085P | 18 | | | | D00373E | D09 | | | 150-199, 275-278 | |
| 219WN | 26 | BW | IS | 0-0 | 34-22-25 | D05085P | 17 | | | | D00373E | C09 | | | ALL | |
| 219Z | | | IS | 0-0 | 34-22-25 | D05085P | 35 | | | | GDZ0003 | S.. | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 26

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1119 | 286T1119 | | | E1-5 SHELF EF1S SG,R (continued) | | | | | | | | | | | | |
| 220B | 24 | PW | IT | 5-0 | 34-22-28 | TB0119G | | 55 | 2 | | | | D00373D | B03 | | 050-099, 280-299 |
| 220B | 24 | PW | IT | 4-0 | 34-22-28 | TB0119G | | 55 | 2 | | | | D00373D | B03 | | 150-199, 275-278 |
| 220R | 24 | PW | IT | 0-0 | 34-22-28 | TB0119G | | 54 | 2 | | | | D00373D | A03 | | ALL |
| 220Z | | | IT | 0-0 | 34-22-28 | GDY0009 | | S.. | 2 | | | | D00373D | DED | | ALL |
| 221B | 24 | PW | IU | 6-0 | 34-22-28 | TB0119F | | C170 | 2 | | | | D00373B | B05 | | 050-099, 280-299 |
| 221B | 24 | PW | IU | 4-4 | 34-22-28 | TB0119F | | C170 | 2 | | | | D00373B | B05 | | 150-199, 275-278 |
| 221R | 24 | PW | IU | 0-0 | 34-22-28 | TB0119F | | A170 | 2 | | | | D00373B | A05 | | ALL |
| 221Z | | | IU | 0-0 | 34-22-28 | GDY0011 | | S.. | 2 | | | | D00373B | DED | | ALL |
| 222B | 24 | PW | IV | 5-0 | 34-22-28 | TB0119G | | 31 | 2 | | | | D00373D | B05 | | 050-099, 280-299 |
| 222B | 24 | PW | IV | 3-6 | 34-22-28 | TB0119G | | 31 | 2 | | | | D00373D | B05 | | 150-199, 275-278 |
| 222R | 24 | PW | IV | 0-0 | 34-22-28 | TB0119G | | 30 | 2 | | | | D00373D | A05 | | ALL |
| 222Z | | | IV | 0-0 | 34-22-28 | GDY0006 | | S.. | 2 | | | | D00373D | DED | | ALL |
| 223B | 24 | PW | IW | 6-0 | 34-22-28 | TB0119Y | | C081 | BJ | | | | D00373A | B03 | | 050-099, 280-299 |
| 223B | 24 | PW | IW | 4-8 | 34-22-28 | TB0119Y | | C081 | BJ | | | | D00373A | B03 | | 150-199, 275-278 |
| 223R | 24 | PW | IW | 0-0 | 34-22-28 | TB0119Y | | A081 | BJ | | | | D00373A | A03 | | ALL |
| 223Z | | | IW | 0-0 | 34-22-28 | GDY0012 | | S.. | 2 | | | | D00373A | DED | | ALL |
| 224B | 24 | PW | IX | 3-0 | 34-22-29 | TB0119G | | 13 | 2 | | | | D00373D | K03 | | 050-099, 280-299 |
| 224B | 24 | PW | IX | 2-2 | 34-22-29 | TB0119G | | 13 | 2 | | | | D00373D | K03 | | 150-199, 275-278 |
| 224R | 24 | PW | IX | 0-0 | 34-22-29 | TB0119G | | 12 | 2 | | | | D00373D | J03 | | ALL |
| 224Z | | | IX | 0-0 | 34-22-29 | GDY0002 | | S.. | 2 | | | | D00373D | DED | | ALL |
| 225B | 24 | PW | IY | 5-0 | 34-22-29 | TB0119G | | 29 | 2 | | | | D00373D | H02 | | 050-099, 280-299 |
| 225B | 24 | PW | IY | 3-4 | 34-22-29 | TB0119G | | 29 | 2 | | | | D00373D | H02 | | 150-199, 275-278 |
| 225R | 24 | PW | IY | 0-0 | 34-22-29 | TB0119G | | 28 | 2 | | | | D00373D | G02 | | ALL |
| 225Z | | | IY | 0-0 | 34-22-29 | GDY0006 | | S.. | 2 | | | | D00373D | DED | | ALL |
| 227B | 24 | PW | JB | 3-0 | 34-22-29 | TB0119Y | | C008 | BJ | | | | D00373A | D04 | | 050-099, 280-299 |
| 227B | 24 | PW | JB | 2-2 | 34-22-29 | TB0119Y | | C008 | BJ | | | | D00373A | D04 | | 150-199, 275-278 |
| 227R | 24 | PW | JB | 0-0 | 34-22-29 | TB0119Y | | A008 | BJ | | | | D00373A | C04 | | ALL |
| 227Z | | | JB | 0-0 | 34-22-29 | GDY0002 | | S.. | 2 | | | | D00373A | DED | | ALL |
| 228B | 24 | PW | JC | 3-0 | 34-22-29 | TB0119H | | 3 | 2 | | | | D00373A | K05 | | 050-099, 280-299 |
| 228B | 24 | PW | JC | 2-2 | 34-22-29 | TB0119H | | 3 | 2 | | | | D00373A | K05 | | 150-199, 275-278 |
| 228R | 24 | PW | JC | 0-0 | 34-22-29 | TB0119H | | 1 | 2 | | | | D00373A | J05 | | ALL |
| 228Z | | | JC | 0-0 | 34-22-29 | GDY0001 | | S.. | 2 | | | | D00373A | DED | | ALL |
| 229B | 24 | PW | JD | 3-0 | 34-22-29 | TB0119F | | C007 | 2 | | | | D00373B | H04 | | 050-099 |
| 229B | 24 | PW | JD | 2-2 | 34-22-29 | TB0119Y | | C009 | BJ | | | | D00373B | H04 | | 150, 152-199, 275-278 |
| 229B | 24 | PW | JD | 2-2 | 34-22-29 | TB0119F | | C007 | 2 | | | | D00373B | H04 | | 151 |
| 229B | 24 | PW | JD | 3-0 | 34-22-29 | TB0119Y | | C009 | BJ | | | | D00373B | H04 | | 280-299 |
| 229R | 24 | PW | JD | 0-0 | 34-22-29 | TB0119F | | A007 | 2 | | | | D00373B | G04 | | 050-099, 151 |
| 229R | 24 | PW | JD | 0-0 | 34-22-29 | TB0119Y | | A009 | BJ | | | | D00373B | G04 | | 150, 152-199, 275-299 |
| 229Z | | | JD | 0-0 | 34-22-29 | GDY0001 | | S.. | 2 | | | | D00373B | DED | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 27

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1119 | 286T1119 | | | E1-5 SHELF EF1S SG,R (continued) | | | | | | | | | | | | |
| 231B | 24 | PW | JF | | 5-0 | 34-22-29 | D00373D | B07 | | | | TB0119H | 158 | 2 | | 050-099, 280-299 |
| 231B | 24 | PW | JF | | 3-11 | 34-22-29 | D00373D | B07 | | | | TB0119H | 158 | 2 | | 150-199, 275-278 |
| 231R | 24 | PW | JF | | 0-0 | 34-22-29 | D00373D | A07 | | | | TB0119H | 156 | 2 | | ALL |
| 231Z | | | JF | | 0-0 | 34-22-29 | D00373D | DED | | | | GDY0009 | S.. | 2 | | ALL |
| 232B | 24 | PW | JG | | 5-0 | 34-22-29 | D00373D | K01 | | | | TB0119F | C136 | 2 | | 050-099, 280-299 |
| 232B | 24 | PW | JG | | 3-5 | 34-22-29 | D00373D | K01 | | | | TB0119F | C136 | 2 | | 150-199, 275-278 |
| 232R | 24 | PW | JG | | 0-0 | 34-22-29 | D00373D | J01 | | | | TB0119F | A136 | 2 | | ALL |
| 232Z | | | JG | | 0-0 | 34-22-29 | D00373D | DED | | | | GDY0007 | S.. | 2 | | ALL |
| 233B | 24 | PW | JH | | 5-0 | 34-22-29 | D00373A | K01 | | | | TB0119G | 134 | 2 | | 050-099, 280-299 |
| 233B | 24 | PW | JH | | 3-5 | 34-22-29 | D00373A | K01 | | | | TB0119G | 134 | 2 | | 150-199, 275-278 |
| 233R | 24 | PW | JH | | 0-0 | 34-22-29 | D00373A | J01 | | | | TB0119G | 133 | 2 | | ALL |
| 233Z | | | JH | | 0-0 | 34-22-29 | D00373A | DED | | | | GDY0006 | S.. | 2 | | ALL |
| 234B | 24 | PW | JI | | 5-0 | 22-12-31 | D00373B | B01 | | | | TB0119F | C146 | 2 | | 050-099, 280-299 |
| 234B | 24 | PW | JI | | 3-7 | 22-12-31 | D00373B | B01 | | | | TB0119F | C146 | 2 | | 150-199, 275-278 |
| 234R | 24 | PW | JI | | 0-0 | 22-12-31 | D00373B | A01 | | | | TB0119F | A146 | 2 | | ALL |
| 234Z | | | JI | | 0-0 | 22-12-31 | D00373B | DED | | | | GDY0008 | S.. | 2 | | ALL |
| 235W | 24 | 7K | JJ | | 0-6 | 34-43-21 | D00373A | E03 | | | | TB0211G | 2 | 2 | | ALL |
| 235WB | 24 | 7K | JJ | | 0-0 | 34-43-21 | D00373A | F03 | | | | TB0211G | 1 | 2 | | ALL |
| 235Z | | | JJ | | 0-0 | 34-43-21 | D00373A | DED | | | | GDZ0001 | S.. | 2 | | ALL |
| 236B | 24 | PW | JK | | 4-0 | 22-12-11 | D00373A | B01 | | | | TB0119F | C118 | 2 | | 050-099, 280-299 |
| 236B | 24 | PW | JK | | 2-7 | 22-12-11 | D00373A | B01 | | | | TB0119F | C118 | 2 | | 150-199, 275-278 |
| 236R | 24 | PW | JK | | 0-0 | 22-12-11 | D00373A | A01 | | | | TB0119F | A118 | 2 | | ALL |
| 236Z | | | JK | | 0-0 | 22-12-11 | D00373A | DED | | | | GDY0002 | S.. | 2 | | ALL |
| 237B | 24 | PW | JL | | 5-0 | 22-12-21 | D00373D | B01 | | | | TB0119G | 42 | 2 | | 050-099, 280-299 |
| 237B | 24 | PW | JL | | 3-8 | 22-12-21 | D00373D | B01 | | | | TB0119G | 42 | 2 | | 150-199, 275-278 |
| 237R | 24 | PW | JL | | 0-0 | 22-12-21 | D00373D | A01 | | | | TB0119G | 41 | 2 | | ALL |
| 237Z | | | JL | | 0-0 | 22-12-21 | D00373D | DED | | | | GDY0007 | S.. | 2 | | ALL |
| 238W | 24 | 7K | JM | | 0-6 | 34-43-21 | D00373D | E03 | | | | TB0211G | 4 | 2 | | ALL |
| 238WB | 24 | 7K | JM | | 0-0 | 34-43-21 | D00373D | F03 | | | | TB0211G | 3 | 2 | | ALL |
| 238Z | | | JM | | 0-0 | 34-43-21 | D00373D | DED | | | | GDZ0001 | S.. | 2 | | ALL |
| 239 | 20 | UA | | | 1-6 | 34-22-23 | GDX0001 | S.. | 2 | | | D00373E | | | JN | 050-099 |
| 239 | 20 | UA | | | 3-0 | 34-22-23 | GDX0001 | S.. | 2 | | | D00373E | | | JN | 150-199, 275-299 |
| 239B | 24 | PW | JN | | 3-0 | 34-22-23 | D05647P | | 2 | | | D00373E | B13 | | | ALL |
| 239R | 24 | PW | JN | | 0-0 | 34-22-23 | D05647P | | 1 | | | D00373E | A13 | | | ALL |
| 239Z | | | JN | | 0-0 | 34-22-23 | D05647P | | 3 | | | D00373E | | | JN | ALL |
| 240B | 24 | PW | JO | | 6-0 | 34-22-24 | D05081P | | 40 | | | TB0119H | 63 | 2 | | 050-099, 280-299 |
| 240B | 24 | PW | JO | | 4-10 | 34-22-24 | D05081P | | 40 | | | TB0119H | 63 | 2 | | 150-199, 275-278 |
| 240R | 24 | PW | JO | | 0-0 | 34-22-24 | D05081P | | 39 | | | TB0119H | 61 | 2 | | ALL |
| 240Z | | | JO | | 0-0 | 34-22-24 | D05081P | | 41 | | | GDY0010 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 28

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1119 | 286T1119 | | | E1-5 SHELF EF1S SG,R (continued) | | | | | | | | | | | |
| 241B | 24 | PW | JP | | 4-0 | 34-22-28 | D00373A | H06 | | | TB0119F | C020 | 2 | | ALL |
| 241R | 24 | PW | JP | | 0-0 | 34-22-28 | D00373A | G06 | | | TB0119F | A020 | 2 | | ALL |
| 241Z | | | JP | | 0-0 | 34-22-28 | D00373A | DED | | | GDY0002 | S.. | 2 | | ALL |
| 242B | 24 | PW | JQ | | 3-0 | 34-22-28 | D00373D | H06 | | | TB0119G | 6 | 2 | | 050-099, 280-299 |
| 242B | 24 | PW | JQ | | 2-2 | 34-22-28 | D00373D | H06 | | | TB0119G | 6 | 2 | | 150-199, 275-278 |
| 242R | 24 | PW | JQ | | 0-0 | 34-22-28 | D00373D | G06 | | | TB0119G | 5 | 2 | | ALL |
| 242Z | | | JQ | | 0-0 | 34-22-28 | D00373D | DED | | | GDY0001 | S.. | 2 | | ALL |
| 243 | 20 | UA | | | 1-6 | 34-22-23 | GDY0001 | S.. | 2 | | D00373A | | | JS | 050-099 |
| 243 | 20 | UA | | | 3-0 | 34-22-23 | GDY0001 | S.. | 2 | | D00373A | | | JS | 150-199, 275-299 |
| 243B | 24 | PW | JS | | 3-0 | 34-22-23 | D05647P | 5 | | | D00373A | D02 | | | ALL |
| 243R | 24 | PW | JS | | 0-0 | 34-22-23 | D05647P | 4 | | | D00373A | C02 | | | ALL |
| 243Z | | | JS | | 0-0 | 34-22-23 | D05647P | 6 | | | D00373A | | | JS | ALL |
| 244 | 20 | UA | | | 1-6 | 34-22-23 | GDY0001 | S.. | 2 | | D00373D | | | JT | 050-099 |
| 244 | 20 | UA | | | 2-0 | 34-22-23 | GDY0001 | S.. | 2 | | D00373D | | | JT | 150-199 |
| 244 | 20 | UA | | | 3-0 | 34-22-23 | GDY0001 | S.. | 2 | | D00373D | | | JT | 275-299 |
| 244B | 24 | PW | JT | | 3-0 | 34-22-23 | D05647P | 8 | | | D00373D | D02 | | | ALL |
| 244R | 24 | PW | JT | | 0-0 | 34-22-23 | D05647P | 7 | | | D00373D | C02 | | | ALL |
| 244Z | | | JT | | 0-0 | 34-22-23 | D05647P | 9 | | | D00373D | | | JT | ALL |
| 501W | 26 | BW | UA | | 3-0 | 34-22-34 | D00373B | B07 | | | D05677P | 2 | | | 050-099, 280-299 |
| 501W | 26 | BW | UA | | 2-0 | 34-22-34 | D00373B | B07 | | | D05677P | 2 | | | 150-199, 275-278 |
| 501WN | 26 | BW | UA | | 0-0 | 34-22-34 | D00373B | A07 | | | D05677P | 1 | | | ALL |
| 501Z | | | UA | | 0-0 | 34-22-34 | GDZ0003 | S.. | 2 | | D05677P | 3 | | | ALL |
| 502W | 26 | BW | UB | | 3-0 | 34-22-34 | D00373B | B08 | | | D05677P | 5 | | | 050-099, 280-299 |
| 502W | 26 | BW | UB | | 2-0 | 34-22-34 | D00373B | B08 | | | D05677P | 5 | | | 150-199, 275-278 |
| 502WN | 26 | BW | UB | | 0-0 | 34-22-34 | D00373B | A08 | | | D05677P | 4 | | | ALL |
| 502Z | | | UB | | 0-0 | 34-22-34 | GDZ0003 | S.. | 2 | | D05677P | 6 | | | ALL |
| 503W | 26 | BW | UC | | 3-0 | 34-22-34 | D00373B | B09 | | | D05677P | 8 | | | 050-099, 280-299 |
| 503W | 26 | BW | UC | | 2-0 | 34-22-34 | D00373B | B09 | | | D05677P | 8 | | | 150-199, 275-278 |
| 503WN | 26 | BW | UC | | 0-0 | 34-22-34 | D00373B | A09 | | | D05677P | 7 | | | ALL |
| 503Z | | | UC | | 0-0 | 34-22-34 | GDZ0003 | S.. | 2 | | D05677P | 9 | | | ALL |
| 504W | 26 | BW | UD | | 3-0 | 34-22-34 | D00373B | B10 | | | D05677P | 11 | | | 050-099, 280-299 |
| 504W | 26 | BW | UD | | 2-0 | 34-22-34 | D00373B | B10 | | | D05677P | 11 | | | 150-199, 275-278 |
| 504WN | 26 | BW | UD | | 0-0 | 34-22-34 | D00373B | A10 | | | D05677P | 10 | | | ALL |
| 504Z | | | UD | | 0-0 | 34-22-34 | GDZ0003 | S.. | 2 | | D05677P | 12 | | | ALL |
| 505W | 26 | BW | UE | | 3-0 | 34-22-34 | D00373B | B11 | | | D05677P | 14 | | | 050-099, 280-299 |
| 505W | 26 | BW | UE | | 2-0 | 34-22-34 | D00373B | B11 | | | D05677P | 14 | | | 150-199, 275-278 |
| 505WN | 26 | BW | UE | | 0-0 | 34-22-34 | D00373B | A11 | | | D05677P | 13 | | | ALL |
| 505Z | | | UE | | 0-0 | 34-22-34 | GDZ0003 | S.. | 2 | | D05677P | 15 | | | ALL |
| 506W | 26 | BW | UF | | 3-0 | 34-22-34 | D00373B | B12 | | | D05677P | 17 | | | 050-099, 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 29

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1119 | 286T1119 | | | E1-5 SHELF EF1S SG,R (continued) | | | | | | | | | | | | |
| 506W | 26 | BW | UF | 2-0 | 34-22-34 | D00373B | B12 | | | | D05677P | 17 | | | 150-199, 275-278 | |
| 506WN | 26 | BW | UF | 0-0 | 34-22-34 | D00373B | A12 | | | | D05677P | 16 | | | ALL | |
| 506Z | | | UF | 0-0 | 34-22-34 | GDZ0003 | S.. | 2 | | | D05677P | 18 | | | ALL | |
| 507W | 26 | BW | UG | 3-0 | 34-22-34 | D00373B | B13 | | | | D05677P | 20 | | | 050-099, 280-299 | |
| 507WN | 26 | BW | UG | 2-0 | 34-22-34 | D00373B | B13 | | | | D05677P | 20 | | | 150-199, 275-278 | |
| 507WN | 26 | BW | UG | 0-0 | 34-22-34 | D00373B | A13 | | | | D05677P | 19 | | | ALL | |
| 507Z | | | UG | 0-0 | 34-22-34 | GDZ0003 | S.. | 2 | | | D05677P | 21 | | | ALL | |
| 508W | 26 | BW | UH | 3-0 | 34-22-34 | D00373B | B14 | | | | D05677P | 23 | | | 050-099, 280-299 | |
| 508WN | 26 | BW | UH | 2-0 | 34-22-34 | D00373B | B14 | | | | D05677P | 23 | | | 150-199, 275-278 | |
| 508WN | 26 | BW | UH | 0-0 | 34-22-34 | D00373B | A14 | | | | D05677P | 22 | | | ALL | |
| 508Z | | | UH | 0-0 | 34-22-34 | GDZ0003 | S.. | 2 | | | D05677P | 24 | | | ALL | |
| 509W | 26 | BW | UI | 3-0 | 34-22-34 | D00373B | B15 | | | | D05677P | 26 | | | 050-099, 280-299 | |
| 509WN | 26 | BW | UI | 2-0 | 34-22-34 | D00373B | B15 | | | | D05677P | 26 | | | 150-199, 275-278 | |
| 509WN | 26 | BW | UI | 0-0 | 34-22-34 | D00373B | A15 | | | | D05677P | 25 | | | ALL | |
| 509Z | | | UI | 0-0 | 34-22-34 | GDZ0003 | S.. | 2 | | | D05677P | 27 | | | ALL | |
| 510W | 26 | BW | UJ | 3-0 | 34-22-34 | D00373B | K07 | | | | D05677P | 29 | | | 050-099, 280-299 | |
| 510WN | 26 | BW | UJ | 2-0 | 34-22-34 | D00373B | K07 | | | | D05677P | 29 | | | 150-199, 275-278 | |
| 510WN | 26 | BW | UJ | 0-0 | 34-22-34 | D00373B | J07 | | | | D05677P | 28 | | | ALL | |
| 510Z | | | UJ | 0-0 | 34-22-34 | GDZ0001 | S.. | 2 | | | D05677P | 30 | | | ALL | |
| 511W | 26 | BW | UK | 3-0 | 34-22-34 | D00373B | K08 | | | | D05677P | 32 | | | 050-099, 280-299 | |
| 511WN | 26 | BW | UK | 2-0 | 34-22-34 | D00373B | K08 | | | | D05677P | 32 | | | 150-199, 275-278 | |
| 511WN | 26 | BW | UK | 0-0 | 34-22-34 | D00373B | J08 | | | | D05677P | 31 | | | ALL | |
| 511Z | | | UK | 0-0 | 34-22-34 | GDZ0001 | S.. | 2 | | | D05677P | 33 | | | ALL | |
| 512W | 26 | BW | UL | 3-0 | 34-22-34 | D00373B | K09 | | | | D05677P | 35 | | | 050-099, 280-299 | |
| 512WN | 26 | BW | UL | 2-0 | 34-22-34 | D00373B | K09 | | | | D05677P | 35 | | | 150-199, 275-278 | |
| 512WN | 26 | BW | UL | 0-0 | 34-22-34 | D00373B | J09 | | | | D05677P | 34 | | | ALL | |
| 512Z | | | UL | 0-0 | 34-22-34 | GDZ0001 | S.. | 2 | | | D05677P | 36 | | | ALL | |
| 513W | 26 | BW | UM | 3-0 | 34-22-34 | D00373B | K10 | | | | D05677P | 38 | | | 050-099, 280-299 | |
| 513WN | 26 | BW | UM | 2-0 | 34-22-34 | D00373B | K10 | | | | D05677P | 38 | | | 150-199, 275-278 | |
| 513WN | 26 | BW | UM | 0-0 | 34-22-34 | D00373B | J10 | | | | D05677P | 37 | | | ALL | |
| 513Z | | | UM | 0-0 | 34-22-34 | GDZ0001 | S.. | 2 | | | D05677P | 39 | | | ALL | |
| 514W | 26 | BW | UN | 3-0 | 34-22-34 | D00373B | K11 | | | | D05677P | 41 | | | 050-099, 280-299 | |
| 514WN | 26 | BW | UN | 2-0 | 34-22-34 | D00373B | K11 | | | | D05677P | 41 | | | 150-199, 275-278 | |
| 514WN | 26 | BW | UN | 0-0 | 34-22-34 | D00373B | J11 | | | | D05677P | 40 | | | ALL | |
| 514Z | | | UN | 0-0 | 34-22-34 | GDZ0001 | S.. | 2 | | | D05677P | 42 | | | ALL | |
| 515W | 26 | BW | UO | 3-0 | 34-22-34 | D00373B | K12 | | | | D05677P | 44 | | | 050-099, 280-299 | |
| 515WN | 26 | BW | UO | 2-0 | 34-22-34 | D00373B | K12 | | | | D05677P | 44 | | | 150-199, 275-278 | |
| 515WN | 26 | BW | UO | 0-0 | 34-22-34 | D00373B | J12 | | | | D05677P | 43 | | | ALL | |
| 515Z | | | UO | 0-0 | 34-22-34 | GDZ0001 | S.. | 2 | | | D05677P | 45 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 30

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|------|----|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1119 | 286T1119 | | | E1-5 SHELF EF1S SG,R (continued) | | | | | | | | | | | | | | |
| 516W | 26 | | BW | UP | 3-0 | 34-22-34 | D00373B | | | | K13 | | | | D05677P | 47 | | 050-099, 280-299 |
| 516W | 26 | | BW | UP | 2-0 | 34-22-34 | D00373B | | | | K13 | | | | D05677P | 47 | | 150-199, 275-278 |
| 516WN | 26 | | BW | UP | 0-0 | 34-22-34 | D00373B | | | | J13 | | | | D05677P | 46 | | ALL |
| 516Z | | | | UP | 0-0 | 34-22-34 | GDZ0001 | | | | S.. | 2 | | | D05677P | 48 | | ALL |
| 517W | 26 | | BW | UQ | 3-0 | 34-22-34 | D00373B | | | | K14 | | | | D05677P | 50 | | 050-099, 280-299 |
| 517W | 26 | | BW | UQ | 2-0 | 34-22-34 | D00373B | | | | K14 | | | | D05677P | 50 | | 150-199, 275-278 |
| 517WN | 26 | | BW | UQ | 0-0 | 34-22-34 | D00373B | | | | J14 | | | | D05677P | 49 | | ALL |
| 517Z | | | | UQ | 0-0 | 34-22-34 | GDZ0001 | | | | S.. | 2 | | | D05677P | 51 | | ALL |
| 518W | 26 | | BW | UR | 3-0 | 34-22-34 | D00373B | | | | K15 | | | | D05677P | 53 | | 050-099, 280-299 |
| 518W | 26 | | BW | UR | 2-0 | 34-22-34 | D00373B | | | | K15 | | | | D05677P | 53 | | 150-199, 275-278 |
| 518WN | 26 | | BW | UR | 0-0 | 34-22-34 | D00373B | | | | J15 | | | | D05677P | 52 | | ALL |
| 518Z | | | | UR | 0-0 | 34-22-34 | GDZ0001 | | | | S.. | 2 | | | D05677P | 54 | | ALL |
| 560B | 24 | | PW | WJ | 3-0 | 34-45-14 | D00373A | | | | K09 | | | | TB0119G | 102 | 2 | 050-099 |
| 560B | 24 | | PW | WJ | 2-2 | 34-45-14 | D00373A | | | | K09 | | | | TB0119G | 102 | 2 | 150-156, 162-166, 275-276 |
| 560B | 24 | | PW | WJ | 2-2 | 34-45-14 | D00373D | | | | K09 | | | | TB0119Y | C101 | BJ | 157, 167-199, 277-278 |
| 560B | 24 | | PW | WJ | 3-0 | 34-45-14 | D00373D | | | | K09 | | | | TB0119Y | C101 | BJ | 280-299 |
| 560R | 24 | | PW | WJ | 0-0 | 34-45-14 | D00373A | | | | J09 | | | | TB0119G | 101 | 2 | 050-099, 150-156, 162-166, 275-276 |
| 560R | 24 | | PW | WJ | 0-0 | 34-45-14 | D00373D | | | | J09 | | | | TB0119Y | A101 | BJ | 157, 167-199, 277-299 |
| 560Z | | | | WJ | 0-0 | 34-45-14 | D00373A | | | | DED | | | | GDY0001 | S.. | 2 | 050-099, 150-156, 162-166, 275-276 |
| 560Z | | | | WJ | 0-0 | 34-45-14 | D00373D | | | | DED | | | | GDY0001 | S.. | 2 | 157, 167-199, 277-299 |
| 601 | 22 | | PA | | 4-0 | 34-22-26 | D00373D | | | | G12 | | | | TB0119F | A117 | 2 | 050-099, 280-299 |
| 601 | 22 | | PA | | 2-7 | 34-22-26 | D00373D | | | | G12 | | | | TB0119F | A117 | 2 | 150-199, 275-278 |
| 604 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | | | G03 | | | | GDX0003 | S.. | # | 050-099 |
| 604 | 22 | | PA | | 2-0 | 34-22-26 | D00373B | | | | G03 | | | | GDX0003 | S.. | # | 150-156, 162-166, 275-276 |
| 604 | 22 | | PA | | 1-11 | 34-22-26 | D00373B | | | | G03 | | | | GDX0002 | S.. | # | 157, 167-199, 277-278 |
| 604 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | | | G03 | | | | GDX0002 | S.. | # | 280-299 |
| 605 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | | | G12 | | | | GDX0003 | S.. | # | 050-099, 150-156, 162-166, 275-276 |
| 605 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | | | G12 | | | | GDX0002 | S.. | # | 157, 167-199, 277-299 |
| 606 | 22 | | PA | | 2-0 | 34-22-26 | D00373B | | | | H03 | | | | GDX0003 | S.. | # | 153-154 |
| 606 | 22 | | PA | | 1-11 | 34-22-26 | D00373B | | | | H03 | | | | GDX0002 | S.. | # | 157, 167-199, 277-278 |
| 606 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | | | H03 | | | | GDX0002 | S.. | # | 280-299 |
| 607 | 22 | | PA | | 2-0 | 34-22-26 | D00373B | | | | J04 | | | | GDX0003 | S.. | # | 153-154 |
| 607 | 22 | | PA | | 1-11 | 34-22-26 | D00373B | | | | J04 | | | | GDX0002 | S.. | # | 157, 167-199, 277-278 |
| 607 | 22 | | PA | | 3-0 | 34-22-26 | D00373B | | | | J04 | | | | GDX0002 | S.. | # | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1110

Page 31

Mar 09/2006



| Bundle No. | Part Number | | | Description | | | From | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|-----------------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | |
| W1119 | 286T1119 | | | E1-5 SHELF EF1S SG,R (continued) | | | | | | | | | | |
| 608 | 22 | | PA | | 2-0 | 34-22-26 | D00373A | | B10 | | GDX0003 | S.. | # | 153-154 |
| 608 | 22 | | PA | | 1-11 | 34-22-26 | D00373A | | B10 | | GDX0002 | S.. | # | 157, 167-199, 277-278 |
| 608 | 22 | | PA | | 3-0 | 34-22-26 | D00373A | | B10 | | GDX0002 | S.. | # | 280-299 |
| 609 | 22 | | PA | | 2-0 | 34-22-26 | D00373B | | B02 | | GDX0003 | S.. | # | 153-154 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1120 | 286T1120 | | | E2-1 WINDOW HEAT RIGHT FWD & LEFT SIDE | | | | | | | | | | | | | |
| 001 | 12 | | PA | | 2-7 | 30-41-12 | D02898B | | 6 | | | | D04294P | | 8 | | ALL |
| 002 | 12 | | PA | | 2-7 | 30-41-12 | D02898B | | 3 | | | | D04294P | | 10 | | ALL |
| 003 | 24 | | PK | | 2-9 | 30-41-12 | D02898A | | 12 | | | | D05932P | | 2 | | ALL |
| 004 | 22 | | PA | | 2-9 | 30-41-12 | D02898A | | 9 | | | | D05932P | | 4 | | ALL |
| 005 | 24 | | PK | | 2-9 | 30-41-12 | D02898A | | 7 | | | | D05932P | | 3 | | ALL |
| 006 | 22 | | PA | | 2-9 | 30-41-12 | D02898A | | 8 | | | | D05932P | | 6 | | ALL |
| 007 | 24 | | PK | | 2-9 | 30-41-12 | D02898A | | 6 | | | | D05932P | | 5 | | ALL |
| 008 | 24 | | PK | | 2-9 | 30-41-12 | D02898A | | 10 | | | | D05932P | | 7 | | ALL |
| 010 | 20 | | UA | | 1-6 | 30-41-12 | D02898A | | | | FA | | GDX0014 | S.. | 2 | | ALL |
| 011 | 20 | | PA | | 2-8 | 30-41-12 | D02898A | | 3 | | | | D04294P | | 13 | | ALL |
| 012 | 20 | | PA | | 2-8 | 30-41-12 | D02898A | | 4 | | | | D04294P | | 22 | | ALL |
| 013 | 20 | | PA | | 2-8 | 30-41-12 | D02898A | | 5 | | | | D04294P | | 30 | | ALL |
| 014 | 20 | | PA | | 2-8 | 30-41-12 | D02898A | | 11 | | | | D04294P | | 14 | | ALL |
| 015 | 20 | | UA | | 1-6 | 30-41-12 | D02898A | | | | FB | | GDX0014 | S.. | 2 | | ALL |
| 016 | 20 | | PA | | 2-8 | 30-41-12 | D02898A | | 16 | | | | D04294P | | 21 | | ALL |
| 017 | 20 | | UA | | 1-6 | 30-41-12 | D02898A | | | | FC | | GDX0014 | S.. | 2 | | ALL |
| 201B | 12 | | PB | A | 2-7 | 30-41-12 | D02898B | | 1 | | | | D04294P | | 2 | | ALL |
| 201R | 12 | | PB | A | 0-0 | 30-41-12 | D02898B | | 2 | | | | D04294P | | 1 | | ALL |
| 202B | 20 | | PB | B | 2-8 | 30-41-12 | D02898A | | 1 | | | | D04294P | | 16 | | ALL |
| 202R | 20 | | PB | B | 0-0 | 30-41-12 | D02898A | | 2 | | | | D04294P | | 18 | | ALL |
| 203B | 12 | | PB | C | 2-7 | 30-41-12 | D02898B | | 4 | | | | D04294P | | 4 | | ALL |
| 203R | 12 | | PB | C | 0-0 | 30-41-12 | D02898B | | 5 | | | | D04294P | | 6 | | ALL |
| 204B | 24 | | PW | D | 2-8 | 30-41-12 | D02898A | | 19 | | | | D04294P | | 15 | | ALL |
| 204R | 24 | | PW | D | 0-0 | 30-41-12 | D02898A | | 20 | | | | D04294P | | 29 | | ALL |
| 204Z | | | | D | 0-0 | 30-41-12 | D02898A | | | | FA | | D04294P | | 3 | | ALL |
| 205B | 24 | | PW | E | 2-8 | 30-41-12 | D02898A | | 13 | | | | D04294P | | 28 | | ALL |
| 205R | 24 | | PW | E | 0-0 | 30-41-12 | D02898A | | 14 | | | | D04294P | | 17 | | ALL |
| 205Z | | | | E | 0-0 | 30-41-12 | D02898A | | | | FB | | D04294P | | 5 | | ALL |
| 206B | 24 | | PW | F | 2-8 | 30-41-12 | D02898A | | 17 | | | | D04294P | | 25 | | ALL |
| 206R | 24 | | PW | F | 0-0 | 30-41-12 | D02898A | | 18 | | | | D04294P | | 26 | | ALL |
| 206Z | | | | F | 0-0 | 30-41-12 | D02898A | | | | FC | | D04294P | | 7 | | ALL |
| W1121 | 286T1121 | | | E1-1 | | | | | | | | | | | | | |
| 201B | 22 | | PB | IA | 5-0 | 27-09-11 | D01251B | | A10 | | | | D01253B | | C10 | | ALL |
| 201R | 22 | | PB | IA | 0-0 | 27-09-11 | D01251B | | C10 | | | | D01253B | | A10 | | ALL |
| W1123 | 286T1123 | | | AFT CABIN LOWERED CEILING LEFT DOOR AREA | | | | | | | | | | | | | |
| 051 | 22 | | PA | | 3-0 | 23-42-11 | D04121P | | 1 | | | | L00197 | = P | \$ | | 050-099, 150-199 |
| 052 | 22 | | PA | | 3-0 | 23-34-13 | D04121P | | 2 | | | | L00583 | = P | \$ | | 050-099, 150-199 |

WIRE LIST
D280T132

91-21-11
Section W1120
Page 1
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1123 | 286T1123 | | | AFT CABIN LOWERED CEILING LEFT DOOR AREA (continued) | | | | | | | | | | | | |
| 053 | 22 | | PA | 3-0 | 33-25-11 | D04121P | | 3 | | | L00569 | = P | \$ | | 050-099, 150-199 | |
| 054 | 20 | | PA | 3-0 | 23-42-11 | D04121P | | 4 | | | L00197 | = G | \$ | | 050-099, 150-199 | |
| W1125 | 286T1125 | | | AFT CABIN LOWERED CEILING RIGHT DOOR AREA | | | | | | | | | | | | |
| 051 | 22 | | PA | 3-0 | 23-42-11 | D04123P | | 1 | | | L00198 | = P | \$ | | 050-099, 150-199 | |
| 052 | 22 | | PA | 3-0 | 23-34-13 | D04123P | | 2 | | | L00584 | = P | \$ | | 050-099, 150-199 | |
| 053 | 22 | | PA | 3-0 | 33-25-11 | D04123P | | 3 | | | L00568 | = P | \$ | | 050-099, 150-199 | |
| 054 | 20 | | PA | 3-0 | 23-42-11 | D04123P | | 4 | | | L00198 | = G | \$ | | 050-099, 150-199 | |
| W1127 | 286T1127 | | | E1-4 SHELF EF1S SG,C | | | | | | | | | | | | |
| 001 | 24 | | PK | 4-0 | 34-22-35 | D05079P | | 1 | | | D00413A | A09 | | | ALL | |
| 002 | 24 | | PK | 4-0 | 34-22-35 | D05079P | | 2 | | | D00413A | B09 | | | ALL | |
| 003 | 24 | | PK | 4-0 | 34-22-35 | D05079P | | 3 | | | D00413A | C09 | | | ALL | |
| 005 | 24 | | PK | 4-0 | 34-22-35 | D05079P | | 8 | | | D00413A | F09 | | | ALL | |
| 006 | 24 | | PK | 4-0 | 34-22-35 | D05079P | | 7 | | | D00413A | G09 | | | ALL | |
| 007 | 24 | | PK | 4-0 | 34-22-35 | D05079P | | 6 | | | D00413A | H09 | | | ALL | |
| 008 | 24 | | PK | 4-0 | 34-22-34 | D05389P | | 1 | | | D00413D | A09 | | | ALL | |
| 009 | 24 | | PK | 4-0 | 34-22-34 | D05389P | | 2 | | | D00413D | B09 | | | ALL | |
| 010 | 24 | | PK | 4-0 | 34-22-34 | D05389P | | 3 | | | D00413D | C09 | | | ALL | |
| 012 | 24 | | PK | 4-0 | 34-22-34 | D05389P | | 8 | | | D00413D | F09 | | | ALL | |
| 013 | 24 | | PK | 4-0 | 34-22-34 | D05389P | | 7 | | | D00413D | G09 | | | ALL | |
| 014 | 24 | | PK | 4-0 | 34-22-34 | D05389P | | 6 | | | D00413D | H09 | | | ALL | |
| 016 | 24 | | PV | AP | 4-0 | 34-22-36 | D00413C | | 1 | | TB0127F | A117 | 2 | | ALL | |
| 016Z | | | | AP | 0-0 | 34-22-36 | D00413C | | DED | | TB0127F | DED | | | ALL | |
| 017 | 20 | | PA | | 3-0 | 34-22-36 | D00413C | | 4 | | GDX0004 | A.. | 2 | | ALL | |
| 018 | 20 | | PA | | 3-0 | 34-22-36 | D00413C | | 6 | | GDX0005 | S.. | 2 | | ALL | |
| 019 | 24 | | PV | AS | 4-0 | 34-22-38 | D00413A | | G12 | | TB0127Y | A119 | BJ | | ALL | |
| 019Z | | | | AS | 0-0 | 34-22-38 | D00413A | | DED | | TB0127Y | DED | | | ALL | |
| 020 | 22 | | PA | | 3-0 | 34-22-37 | D00413D | | J11 | | GDX0005 | D.. | 2 | | ALL | |
| 021 | 22 | | PA | | 3-0 | 34-22-37 | D00413D | | A12 | | GDX0005 | D.. | 2 | | ALL | |
| 023 | 22 | | PA | | 3-0 | 34-22-37 | D00413D | | C11 | | GDX0005 | D.. | 2 | | ALL | |
| 024 | 24 | | PV | AX | 5-0 | 34-22-37 | D00413A | | F12 | | TB0127F | A155 | 2 | | ALL | |
| 024Z | | | | AX | 0-0 | 34-22-37 | D00413A | | DED | | TB0127F | DED | | | ALL | |
| 025 | 24 | | PV | AY | 4-0 | 34-22-37 | D00413A | | J12 | | TB0127Y | A120 | BJ | | ALL | |
| 025Z | | | | AY | 0-0 | 34-22-37 | D00413A | | DED | | TB0127Y | DED | | | ALL | |
| 026 | 24 | | PV | BA | 4-0 | 34-22-37 | D00413A | | K12 | | TB0127Y | C120 | BJ | | ALL | |
| 026Z | | | | BA | 0-0 | 34-22-37 | D00413A | | DED | | TB0127Y | DED | | | ALL | |
| 027 | 24 | | PV | BB | 4-0 | 34-22-37 | D00413A | | E11 | | TB0127F | A121 | 2 | | ALL | |
| 027Z | | | | BB | 0-0 | 34-22-37 | D00413A | | DED | | TB0127F | DED | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1120

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1127 | 286T1127 | | | E1-4 SHELF EF1S SG,C (continued) | | | | | | | | | | | |
| 028 | 24 | PV | BC | 4-0 | 34-22-37 | D00413A | G11 | | | | TB0127F | C121 | 2 | | ALL |
| 028Z | | | BC | 0-0 | 34-22-37 | D00413A | DED | | | | TB0127F | DED | | | ALL |
| 029 | 24 | PV | BD | 4-0 | 34-22-37 | D00413D | J12 | | | | TB0127F | A148 | 2 | | ALL |
| 029Z | | | BD | 0-0 | 34-22-37 | D00413D | DED | | | | TB0127F | DED | | | ALL |
| 030 | 24 | PV | BE | 4-0 | 34-22-37 | D00413D | E11 | | | | TB0127F | C148 | 2 | | ALL |
| 030Z | | | BE | 0-0 | 34-22-37 | D00413D | DED | | | | TB0127F | DED | | | ALL |
| 031 | 24 | PV | BF | 4-0 | 34-22-37 | D00413D | K12 | | | | TB0127F | A149 | 2 | | ALL |
| 031Z | | | BF | 0-0 | 34-22-37 | D00413D | DED | | | | TB0127F | DED | | | ALL |
| 032 | 24 | PV | BG | 4-0 | 34-22-37 | D00413D | G11 | | | | TB0127F | C149 | 2 | | ALL |
| 032Z | | | BG | 0-0 | 34-22-37 | D00413D | DED | | | | TB0127F | DED | | | ALL |
| 033 | 22 | PQ | BH | 4-0 | 34-31-31 | D00413A | E12 | | | | TB0127G | 23 | 2 | | ALL |
| 033Z | | | BH | 0-0 | 34-31-31 | D00413A | DED | | | | TB0127G | DED | | | ALL |
| 034 | 24 | PK | | 4-0 | 33-16-14 | D00413D | B12 | | | | TB0127F | C125 | 2 | | ALL |
| 035 | 20 | PA | | 3-0 | 34-22-36 | D00413B | REF | Y | | | GDX0003 | S.. | 2 | | 162-199 |
| 036 | 20 | PA | | 3-0 | 34-22-36 | D00413B | REF | Y | | | GDX0003 | S.. | 2 | | 162-199 |
| 042 | 22 | PA | | 4-0 | 34-22-13 | D00413D | F13 | | | | TB0127F | A113 | 2 | | ALL |
| 056 | 22 | PA | | 3-0 | 34-22-36 | D00413B | E10 | | | | GDX0003 | S.. | 2 | | ALL |
| 067 | 22 | PA | | 6-0 | 34-45-14 | D00413E | G11 | | | | TB0127X | C012 | BJ | | 157, 167-199, 277-299 |
| 068 | 22 | PA | | 4-0 | 34-45-14 | D00413E | E11 | | | | TB0127X | D012 | BJ | | 157, 167-199, 277-299 |
| 091 | 22 | PA | | 3-0 | 34-22-36 | D00413B | F09 | | | | GDX0003 | S.. | 2 | | ALL |
| 092 | 22 | PA | | 3-0 | 34-22-36 | D00413B | G09 | | | | GDX0003 | S.. | 2 | | ALL |
| 094 | 22 | PA | | 4-0 | 34-22-36 | D00413B | D08 | | | | TB0127G | 44 | 2 | | ALL |
| 097 | 22 | PA | | 3-0 | 34-22-36 | D00413B | D10 | | | | GDX0003 | S.. | 2 | | ALL |
| 098 | 22 | PA | | 3-0 | 34-22-36 | D00413B | D12 | | | | GDX0003 | S.. | 2 | | ALL |
| 102 | 22 | PA | | 3-0 | 34-22-36 | D00413B | D11 | | | | GDX0003 | S.. | 2 | | ALL |
| 104 | 24 | PK | | 4-0 | 34-22-37 | D00413D | A11 | | | | TB0127F | A106 | 2 | | ALL |
| 105 | 22 | PA | | 3-0 | 34-22-37 | D00413D | J13 | | | | GDX0003 | D.. | 2 | | ALL |
| 106 | 24 | PK | | 4-0 | 34-22-37 | D00413A | A11 | | | | TB0127F | C106 | 2 | | ALL |
| 107 | 24 | PK | | 4-0 | 34-22-36 | D00413A | K13 | | | | TB0127G | 105 | 2 | | ALL |
| 108 | 22 | PA | | 3-0 | 34-22-36 | D00413D | D12 | | | | GDX0003 | S.. | 2 | | ALL |
| 109 | 22 | PA | | 3-0 | 34-22-36 | D00413B | D05 | | | | GDX0003 | S.. | 2 | | ALL |
| 111 | 24 | PK | | 4-0 | 34-46-12 | D00413E | A11 | | | | TB0127F | A014 | 2 | | 050-099, 150-199, 275-278 |
| 112 | 24 | PK | | 4-0 | 34-22-36 | D00413A | C14 | | | | TB0127G | 105 | 2 | | ALL |
| 115 | 22 | PA | | 3-0 | 34-22-36 | D00413B | K04 | | | | GDX0004 | S.. | 2 | | 156-157, 166-199, 277-299 |
| 123 | 22 | PA | | 3-0 | 34-22-36 | D00413B | F06 | | | | GDX0003 | S.. | 2 | | ALL |
| 125 | 22 | PA | | 3-0 | 34-22-36 | D00413B | B04 | | | | GDX0003 | S.. | 2 | | ALL |
| 126 | 22 | PA | | 3-0 | 34-22-36 | D00413B | G06 | | | | GDX0003 | S.. | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1120
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1127 | 286T1127 | | | E1-4 SHELF EF1S SG,C (continued) | | | | | | | | | | | | |
| 128 | 22 | | PA | | 4-0 | 34-22-36 | D00413A | D14 | | | | TB0127F | C113 | 2 | | ALL |
| 136 | 22 | | PA | | 3-0 | 34-22-36 | D00413B | J05 | | | | GDZ0003 | S.. | 2 | | ALL |
| 201B | 24 | | PW | IA | 4-0 | 34-22-35 | TB0127F | C123 | 2 | | | D00413A | F05 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-22-35 | TB0127F | A123 | 2 | | | D00413A | E05 | | | ALL |
| 201Z | | | | IA | 0-0 | 34-22-35 | GDY0005 | S.. | 2 | | | D00413A | DED | | | 050-099, 152-199, 275-299 |
| 201Z | | | | IA | 0-0 | 34-22-35 | GDY0006 | S.. | 2 | | | D00413A | DED | | | 150-151 |
| 202W | 26 | | BW | IB | 4-0 | 34-22-35 | D04387P | | 2 | | | D00413E | B01 | | | ALL |
| 202WN | 26 | | BW | IB | 0-0 | 34-22-35 | D04387P | | 1 | | | D00413E | A01 | | | ALL |
| 202Z | | | | IB | 0-0 | 34-22-35 | D04387P | | 3 | | | GDZ0002 | S.. | 2 | | ALL |
| 203W | 26 | | BW | IC | 4-0 | 34-22-35 | D04387P | | 5 | | | D00413E | B02 | | | ALL |
| 203WN | 26 | | BW | IC | 0-0 | 34-22-35 | D04387P | | 4 | | | D00413E | A02 | | | ALL |
| 203Z | | | | IC | 0-0 | 34-22-35 | D04387P | | 6 | | | GDZ0003 | S.. | 2 | | ALL |
| 204W | 26 | | BW | ID | 4-0 | 34-22-35 | D04387P | | 8 | | | D00413E | B03 | | | ALL |
| 204WN | 26 | | BW | ID | 0-0 | 34-22-35 | D04387P | | 7 | | | D00413E | A03 | | | ALL |
| 204Z | | | | ID | 0-0 | 34-22-35 | D04387P | | 9 | | | GDZ0003 | S.. | 2 | | ALL |
| 205W | 26 | | BW | IE | 4-0 | 34-22-35 | D04387P | | 11 | | | D00413E | B04 | | | ALL |
| 205WN | 26 | | BW | IE | 0-0 | 34-22-35 | D04387P | | 10 | | | D00413E | A04 | | | ALL |
| 205Z | | | | IE | 0-0 | 34-22-35 | D04387P | | 12 | | | GDZ0003 | S.. | 2 | | ALL |
| 206W | 26 | | BW | IF | 4-0 | 34-22-35 | D04387P | | 14 | | | D00413E | B05 | | | ALL |
| 206WN | 26 | | BW | IF | 0-0 | 34-22-35 | D04387P | | 13 | | | D00413E | A05 | | | ALL |
| 206Z | | | | IF | 0-0 | 34-22-35 | D04387P | | 15 | | | GDZ0003 | S.. | 2 | | ALL |
| 207W | 26 | | BW | IG | 4-0 | 34-22-35 | D04387P | | 17 | | | D00413E | B06 | | | ALL |
| 207WN | 26 | | BW | IG | 0-0 | 34-22-35 | D04387P | | 16 | | | D00413E | A06 | | | ALL |
| 207Z | | | | IG | 0-0 | 34-22-35 | D04387P | | 18 | | | GDZ0003 | S.. | 2 | | ALL |
| 208W | 26 | | BW | IH | 4-0 | 34-22-35 | D04387P | | 20 | | | D00413E | B07 | | | ALL |
| 208WN | 26 | | BW | IH | 0-0 | 34-22-35 | D04387P | | 19 | | | D00413E | A07 | | | ALL |
| 208Z | | | | IH | 0-0 | 34-22-35 | D04387P | | 21 | | | GDZ0003 | S.. | 2 | | ALL |
| 209W | 26 | | BW | II | 4-0 | 34-22-35 | D04387P | | 23 | | | D00413E | B08 | | | ALL |
| 209WN | 26 | | BW | II | 0-0 | 34-22-35 | D04387P | | 22 | | | D00413E | A08 | | | ALL |
| 209Z | | | | II | 0-0 | 34-22-35 | D04387P | | 24 | | | GDZ0003 | S.. | 2 | | ALL |
| 210W | 26 | | BW | IJ | 4-0 | 34-22-35 | D04387P | | 26 | | | D00413E | B09 | | | ALL |
| 210WN | 26 | | BW | IJ | 0-0 | 34-22-35 | D04387P | | 25 | | | D00413E | A09 | | | ALL |
| 210Z | | | | IJ | 0-0 | 34-22-35 | D04387P | | 27 | | | GDZ0003 | S.. | 2 | | ALL |
| 211W | 26 | | BW | IK | 4-0 | 34-22-35 | D04387P | | 29 | | | D00413E | D01 | | | ALL |
| 211WN | 26 | | BW | IK | 0-0 | 34-22-35 | D04387P | | 28 | | | D00413E | C01 | | | ALL |
| 211Z | | | | IK | 0-0 | 34-22-35 | D04387P | | 30 | | | GDZ0002 | S.. | 2 | | ALL |
| 212W | 26 | | BW | IL | 4-0 | 34-22-35 | D04387P | | 32 | | | D00413E | D02 | | | ALL |
| 212WN | 26 | | BW | IL | 0-0 | 34-22-35 | D04387P | | 31 | | | D00413E | C02 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1120

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|----------|---------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1127 | 286T1127 | | | E1-4 SHELF EF1S SG,C (continued) | | | | | | | | | | | |
| 212Z | | | | IL | 0-0 | 34-22-35 | D04387P | | 33 | | GDZ0003 | S.. | 2 | | ALL |
| 213W | 26 | | | BW | IM | 4-0 | 34-22-35 | D04387P | | 35 | D00413E | D03 | | | ALL |
| 213WN | 26 | | | BW | IM | 0-0 | 34-22-35 | D04387P | | 34 | D00413E | C03 | | | ALL |
| 213Z | | | | | IM | 0-0 | 34-22-35 | D04387P | | 36 | GDZ0003 | S.. | 2 | | ALL |
| 214W | 26 | | | BW | IN | 4-0 | 34-22-35 | D04387P | | 38 | D00413E | D04 | | | ALL |
| 214WN | 26 | | | BW | IN | 0-0 | 34-22-35 | D04387P | | 37 | D00413E | C04 | | | ALL |
| 214Z | | | | | IN | 0-0 | 34-22-35 | D04387P | | 39 | GDZ0003 | S.. | 2 | | ALL |
| 215W | 26 | | | BW | IO | 4-0 | 34-22-35 | D04387P | | 41 | D00413E | D05 | | | ALL |
| 215WN | 26 | | | BW | IO | 0-0 | 34-22-35 | D04387P | | 40 | D00413E | C05 | | | ALL |
| 215Z | | | | | IO | 0-0 | 34-22-35 | D04387P | | 42 | GDZ0003 | S.. | 2 | | ALL |
| 216W | 26 | | | BW | IP | 4-0 | 34-22-35 | D04387P | | 44 | D00413E | D06 | | | ALL |
| 216WN | 26 | | | BW | IP | 0-0 | 34-22-35 | D04387P | | 43 | D00413E | C06 | | | ALL |
| 216Z | | | | | IP | 0-0 | 34-22-35 | D04387P | | 45 | GDZ0003 | S.. | 2 | | ALL |
| 217W | 26 | | | BW | IQ | 4-0 | 34-22-35 | D04387P | | 47 | D00413E | D07 | | | ALL |
| 217WN | 26 | | | BW | IQ | 0-0 | 34-22-35 | D04387P | | 46 | D00413E | C07 | | | ALL |
| 217Z | | | | | IQ | 0-0 | 34-22-35 | D04387P | | 48 | GDZ0003 | S.. | 2 | | ALL |
| 218W | 26 | | | BW | IR | 4-0 | 34-22-35 | D04387P | | 50 | D00413E | D08 | | | ALL |
| 218WN | 26 | | | BW | IR | 0-0 | 34-22-35 | D04387P | | 49 | D00413E | C08 | | | ALL |
| 218Z | | | | | IR | 0-0 | 34-22-35 | D04387P | | 51 | GDZ0003 | S.. | 2 | | ALL |
| 219W | 26 | | | BW | IS | 4-0 | 34-22-35 | D04387P | | 53 | D00413E | D09 | | | ALL |
| 219WN | 26 | | | BW | IS | 0-0 | 34-22-35 | D04387P | | 52 | D00413E | C09 | | | ALL |
| 219Z | | | | | IS | 0-0 | 34-22-35 | D04387P | | 54 | GDZ0003 | S.. | 2 | | ALL |
| 220B | 24 | | | PW | IT | 4-0 | 34-22-34 | D00413D | F05 | | TB0127F | C145 | 2 | | ALL |
| 220R | 24 | | | PW | IT | 0-0 | 34-22-34 | D00413D | E05 | | TB0127F | A145 | 2 | | ALL |
| 220Z | | | | | IT | 0-0 | 34-22-34 | GDY0008 | S.. | 2 | D00413D | DED | | | ALL |
| 221W | 26 | | | BW | IU | 3-0 | 34-22-34 | D05677J | | 2 | D00413E | K01 | | | ALL |
| 221WN | 26 | | | BW | IU | 0-0 | 34-22-34 | D05677J | | 1 | D00413E | J01 | | | ALL |
| 221Z | | | | | IU | 0-0 | 34-22-34 | D05677J | | 3 | GDZ0002 | S.. | 2 | | ALL |
| 222W | 26 | | | BW | IV | 3-0 | 34-22-34 | D05677J | | 5 | D00413E | K02 | | | ALL |
| 222WN | 26 | | | BW | IV | 0-0 | 34-22-34 | D05677J | | 4 | D00413E | J02 | | | ALL |
| 222Z | | | | | IV | 0-0 | 34-22-34 | D05677J | | 6 | GDZ0002 | S.. | 2 | | ALL |
| 223W | 26 | | | BW | IW | 3-0 | 34-22-34 | D05677J | | 8 | D00413E | K03 | | | ALL |
| 223WN | 26 | | | BW | IW | 0-0 | 34-22-34 | D05677J | | 7 | D00413E | J03 | | | ALL |
| 223Z | | | | | IW | 0-0 | 34-22-34 | D05677J | | 9 | GDZ0002 | S.. | 2 | | ALL |
| 224W | 26 | | | BW | IX | 3-0 | 34-22-34 | D05677J | | 11 | D00413E | K04 | | | ALL |
| 224WN | 26 | | | BW | IX | 0-0 | 34-22-34 | D05677J | | 10 | D00413E | J04 | | | ALL |
| 224Z | | | | | IX | 0-0 | 34-22-34 | D05677J | | 12 | GDZ0002 | S.. | 2 | | ALL |
| 225W | 26 | | | BW | IY | 3-0 | 34-22-34 | D05677J | | 14 | D00413E | K05 | | | ALL |
| 225WN | 26 | | | BW | IY | 0-0 | 34-22-34 | D05677J | | 13 | D00413E | J05 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1120
Page 5
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1127 | 286T1127 | | | E1-4 SHELF EF1S SG,C (continued) | | | | | | | | | | | |
| 225Z | | | IY | 0-0 | 34-22-34 | D05677J | | | 15 | | GDZ0002 | S.. | 2 | | ALL |
| 226W | 26 | BW | JA | 3-0 | 34-22-34 | D05677J | | | 17 | | D00413E | K06 | | | ALL |
| 226WN | 26 | BW | JA | 0-0 | 34-22-34 | D05677J | | | 16 | | D00413E | J06 | | | ALL |
| 226Z | | | JA | 0-0 | 34-22-34 | D05677J | | | 18 | | GDZ0002 | S.. | 2 | | ALL |
| 227W | 26 | BW | JB | 3-0 | 34-22-34 | D05677J | | | 20 | | D00413E | K07 | | | ALL |
| 227WN | 26 | BW | JB | 0-0 | 34-22-34 | D05677J | | | 19 | | D00413E | J07 | | | ALL |
| 227Z | | | JB | 0-0 | 34-22-34 | D05677J | | | 21 | | GDZ0002 | S.. | 2 | | ALL |
| 228W | 26 | BW | JC | 3-0 | 34-22-34 | D05677J | | | 23 | | D00413E | K08 | | | ALL |
| 228WN | 26 | BW | JC | 0-0 | 34-22-34 | D05677J | | | 22 | | D00413E | J08 | | | ALL |
| 228Z | | | JC | 0-0 | 34-22-34 | D05677J | | | 24 | | GDZ0001 | S.. | 2 | | ALL |
| 229W | 26 | BW | JD | 3-0 | 34-22-34 | D05677J | | | 26 | | D00413E | K09 | | | ALL |
| 229WN | 26 | BW | JD | 0-0 | 34-22-34 | D05677J | | | 25 | | D00413E | J09 | | | ALL |
| 229Z | | | JD | 0-0 | 34-22-34 | D05677J | | | 27 | | GDZ0001 | S.. | 2 | | ALL |
| 230W | 26 | BW | JE | 3-0 | 34-22-34 | D05677J | | | 29 | | D00413E | H01 | | | ALL |
| 230WN | 26 | BW | JE | 0-0 | 34-22-34 | D05677J | | | 28 | | D00413E | G01 | | | ALL |
| 230Z | | | JE | 0-0 | 34-22-34 | D05677J | | | 30 | | GDZ0002 | S.. | 2 | | ALL |
| 231W | 26 | BW | JF | 3-0 | 34-22-34 | D05677J | | | 32 | | D00413E | H02 | | | ALL |
| 231WN | 26 | BW | JF | 0-0 | 34-22-34 | D05677J | | | 31 | | D00413E | G02 | | | ALL |
| 231Z | | | JF | 0-0 | 34-22-34 | D05677J | | | 33 | | GDZ0002 | S.. | 2 | | ALL |
| 232W | 26 | BW | JG | 3-0 | 34-22-34 | D05677J | | | 35 | | D00413E | H03 | | | ALL |
| 232WN | 26 | BW | JG | 0-0 | 34-22-34 | D05677J | | | 34 | | D00413E | G03 | | | ALL |
| 232Z | | | JG | 0-0 | 34-22-34 | D05677J | | | 36 | | GDZ0002 | S.. | 2 | | ALL |
| 233W | 26 | BW | JH | 3-0 | 34-22-34 | D05677J | | | 38 | | D00413E | H04 | | | ALL |
| 233WN | 26 | BW | JH | 0-0 | 34-22-34 | D05677J | | | 37 | | D00413E | G04 | | | ALL |
| 233Z | | | JH | 0-0 | 34-22-34 | D05677J | | | 39 | | GDZ0002 | S.. | 2 | | ALL |
| 234W | 26 | BW | JI | 3-0 | 34-22-34 | D05677J | | | 41 | | D00413E | H05 | | | ALL |
| 234WN | 26 | BW | JI | 0-0 | 34-22-34 | D05677J | | | 40 | | D00413E | G05 | | | ALL |
| 234Z | | | JI | 0-0 | 34-22-34 | D05677J | | | 42 | | GDZ0002 | S.. | 2 | | ALL |
| 235W | 26 | BW | JJ | 3-0 | 34-22-34 | D05677J | | | 44 | | D00413E | H06 | | | ALL |
| 235WN | 26 | BW | JJ | 0-0 | 34-22-34 | D05677J | | | 43 | | D00413E | G06 | | | ALL |
| 235Z | | | JJ | 0-0 | 34-22-34 | D05677J | | | 45 | | GDZ0002 | S.. | 2 | | ALL |
| 236W | 26 | BW | JK | 3-0 | 34-22-34 | D05677J | | | 47 | | D00413E | H07 | | | ALL |
| 236WN | 26 | BW | JK | 0-0 | 34-22-34 | D05677J | | | 46 | | D00413E | G07 | | | ALL |
| 236Z | | | JK | 0-0 | 34-22-34 | D05677J | | | 48 | | GDZ0002 | S.. | 2 | | ALL |
| 237W | 26 | BW | JL | 3-0 | 34-22-34 | D05677J | | | 50 | | D00413E | H08 | | | ALL |
| 237WN | 26 | BW | JL | 0-0 | 34-22-34 | D05677J | | | 49 | | D00413E | G08 | | | ALL |
| 237Z | | | JL | 0-0 | 34-22-34 | D05677J | | | 51 | | GDZ0001 | S.. | 2 | | ALL |
| 238W | 26 | BW | JM | 3-0 | 34-22-34 | D05677J | | | 53 | | D00413E | H09 | | | ALL |
| 238WN | 26 | BW | JM | 0-0 | 34-22-34 | D05677J | | | 52 | | D00413E | G09 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1120

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1127 | 286T1127 | | | E1-4 SHELF EF1S SG,C (continued) | | | | | | | | | | | | | |
| 238Z | | | | JM | 0-0 | 34-22-34 | D05677J | | 54 | | | | GDZ0001 | S.. | 2 | | ALL |
| 239B | 24 | PW | | JN | 4-0 | 34-22-38 | D00413A | | B05 | | | | TB0127F | C115 | 2 | | ALL |
| 239R | 24 | PW | | JN | 0-0 | 34-22-38 | D00413A | | A05 | | | | TB0127F | A115 | 2 | | ALL |
| 239Z | | | | JN | 0-0 | 34-22-38 | D00413A | | DED | | | | GDY0002 | S.. | 2 | | ALL |
| 240B | 24 | PW | | JO | 4-0 | 34-22-38 | D00413D | | B05 | | | | TB0127F | C147 | 2 | | ALL |
| 240R | 24 | PW | | JO | 0-0 | 34-22-38 | D00413D | | A05 | | | | TB0127F | A147 | 2 | | ALL |
| 240Z | | | | JO | 0-0 | 34-22-38 | D00413D | | DED | | | | GDY0008 | S.. | 2 | | ALL |
| 241B | 24 | PW | | JP | 4-0 | 34-22-38 | D00413B | | B05 | | | | TB0127G | 19 | 2 | | ALL |
| 241R | 24 | PW | | JP | 0-0 | 34-22-38 | D00413B | | A05 | | | | TB0127G | 18 | 2 | | ALL |
| 241Z | | | | JP | 0-0 | 34-22-38 | D00413B | | DED | | | | GDY0002 | S.. | 2 | | ALL |
| 242 | 20 | UA | | JA | 1-6 | 34-22-38 | D00413D | | REF | | JQ | | GDX0004 | S.. | 2 | | ALL |
| 242B | 24 | PW | | JQ | 5-0 | 34-22-38 | D00413D | | B03 | | | | D02285 | B2 | | | ALL |
| 242R | 24 | PW | | JQ | 0-0 | 34-22-38 | D00413D | | A03 | | | | D02285 | A2 | | | ALL |
| 242Z | | | | JQ | 0-0 | 34-22-38 | D00413D | | REF | | JQ | | D02285 | DED | | | ALL |
| 243B | 24 | PW | | JR | 4-0 | 34-22-39 | D00413B | | H04 | | | | TB0127G | 16 | 2 | | ALL |
| 243R | 24 | PW | | JR | 0-0 | 34-22-39 | D00413B | | G04 | | | | TB0127G | 15 | 2 | | ALL |
| 243Z | | | | JR | 0-0 | 34-22-39 | D00413B | | DED | | | | GDY0002 | S.. | 2 | | ALL |
| 244B | 24 | PW | | JS | 5-0 | 34-22-39 | D00413D | | H02 | | | | TB0127F | C151 | 2 | | ALL |
| 244R | 24 | PW | | JS | 0-0 | 34-22-39 | D00413D | | G02 | | | | TB0127F | A151 | 2 | | ALL |
| 244Z | | | | JS | 0-0 | 34-22-39 | D00413D | | DED | | | | GDY0008 | S.. | 2 | | ALL |
| 245B | 24 | PW | | JT | 5-0 | 34-22-39 | D00413D | | K03 | | | | TB0127F | C152 | 2 | | ALL |
| 245R | 24 | PW | | JT | 0-0 | 34-22-39 | D00413D | | J03 | | | | TB0127F | A152 | 2 | | ALL |
| 245Z | | | | JT | 0-0 | 34-22-39 | D00413D | | DED | | | | GDY0009 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 245Z | | | | JT | 0-0 | 34-22-39 | D00413D | | DED | | | | GDY0010 | S.. | 2 | | 150-151 |
| 247B | 24 | PW | | JV | 4-0 | 34-22-39 | D00413A | | D04 | | | | TB0127G | 22 | 2 | | ALL |
| 247R | 24 | PW | | JV | 0-0 | 34-22-39 | D00413A | | C04 | | | | TB0127G | 21 | 2 | | ALL |
| 247Z | | | | JV | 0-0 | 34-22-39 | D00413A | | DED | | | | GDY0005 | S.. | 2 | | ALL |
| 248B | 24 | PW | | JW | 4-0 | 34-22-39 | D00413A | | K05 | | | | TB0127F | C122 | 2 | | ALL |
| 248R | 24 | PW | | JW | 0-0 | 34-22-39 | D00413A | | J05 | | | | TB0127F | A122 | 2 | | ALL |
| 248Z | | | | JW | 0-0 | 34-22-39 | D00413A | | DED | | | | GDY0005 | S.. | 2 | | ALL |
| 250B | 24 | PW | | JY | 4-0 | 34-22-39 | D00413A | | K03 | | | | TB0127F | C126 | 2 | | ALL |
| 250R | 24 | PW | | JY | 0-0 | 34-22-39 | D00413A | | J03 | | | | TB0127F | A126 | 2 | | ALL |
| 250Z | | | | JY | 0-0 | 34-22-39 | D00413A | | DED | | | | GDY0005 | S.. | 2 | | ALL |
| 251B | 24 | PW | | KA | 4-0 | 34-22-39 | D00413A | | H02 | | | | TB0127F | C127 | 2 | | ALL |
| 251R | 24 | PW | | KA | 0-0 | 34-22-39 | D00413A | | G02 | | | | TB0127F | A127 | 2 | | ALL |
| 251Z | | | | KA | 0-0 | 34-22-39 | D00413A | | DED | | | | GDY0005 | S.. | 2 | | ALL |
| 252W | 24 | 7K | | KB | 0-6 | 34-43-21 | D00413D | | E03 | | | | TB0209R | A009 | 2 | | ALL |
| 252WB | 24 | 7K | | KB | 0-0 | 34-43-21 | D00413D | | F03 | | | | TB0209R | C009 | 2 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1120
Page 7
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1127 | 286T1127 | | | E1-4 SHELF EF1S SG,C (continued) | | | | | | | | | | | |
| 252Z | | | | KB | 0-0 | 34-43-21 | D00413D | | DED | | GDZ0001 | S.. | 2 | | ALL |
| 253W | 24 | 7K | | KC | 0-6 | 34-43-21 | D00413A | | E03 | | TB0209R | A008 | 2 | | ALL |
| 253WB | 24 | 7K | | KC | 0-0 | 34-43-21 | D00413A | | F03 | | TB0209R | C008 | 2 | | ALL |
| 253Z | | | | KC | 0-0 | 34-43-21 | D00413A | | DED | | GDZ0001 | S.. | 2 | | ALL |
| 254B | 24 | PW | | KD | 5-0 | 22-12-31 | D00413B | | B01 | | TB0127G | 57 | 2 | | ALL |
| 254R | 24 | PW | | KD | 0-0 | 22-12-31 | D00413B | | A01 | | TB0127G | 56 | 2 | | ALL |
| 254Z | | | | KD | 0-0 | 22-12-31 | D00413B | | DED | | GDY0009 | S.. | 2 | | ALL |
| 255B | 24 | PW | | KE | 6-0 | 34-22-38 | D00413A | | B03 | | TB0127Y | C181 | BJ | | ALL |
| 255R | 24 | PW | | KE | 0-0 | 34-22-38 | D00413A | | A03 | | TB0127Y | A181 | BJ | | ALL |
| 255Z | | | | KE | 0-0 | 34-22-38 | D00413A | | DED | | GDY0012 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 255Z | | | | KE | 0-0 | 34-22-38 | D00413A | | DED | | GDY0011 | S.. | 2 | | 150-151 |
| 256W | 24 | 7K | | KF | 0-6 | 34-43-11 | D00413A | | E01 | | TB0209R | A007 | 2 | | ALL |
| 256WB | 24 | 7K | | KF | 0-0 | 34-43-11 | D00413A | | F01 | | TB0209R | C007 | 2 | | ALL |
| 256Z | | | | KF | 0-0 | 34-43-11 | D00413A | | DED | | GDZ0001 | S.. | 2 | | ALL |
| 257W | 24 | 7K | | KG | 0-6 | 34-43-11 | D00413D | | E01 | | TB0209R | A006 | 2 | | ALL |
| 257WB | 24 | 7K | | KG | 0-0 | 34-43-11 | D00413D | | F01 | | TB0209R | C006 | 2 | | ALL |
| 257Z | | | | KG | 0-0 | 34-43-11 | D00413D | | DED | | GDZ0001 | S.. | 2 | | ALL |
| 258B | 24 | PW | | KH | 4-0 | 34-22-39 | D00413A | | B07 | | TB0127F | C101 | 2 | | ALL |
| 258R | 24 | PW | | KH | 0-0 | 34-22-39 | D00413A | | A07 | | TB0127F | A101 | 2 | | ALL |
| 258Z | | | | KH | 0-0 | 34-22-39 | D00413A | | DED | | GDY0001 | S.. | 2 | | ALL |
| 259B | 24 | PW | | KI | 4-0 | 34-22-39 | D00413D | | B07 | | TB0127F | C102 | 2 | | ALL |
| 259R | 24 | PW | | KI | 0-0 | 34-22-39 | D00413D | | A07 | | TB0127F | A102 | 2 | | ALL |
| 259Z | | | | KI | 0-0 | 34-22-39 | D00413D | | DED | | GDY0001 | S.. | 2 | | ALL |
| 260B | 24 | PW | | KJ | 4-0 | 22-12-11 | D00413A | | B01 | | TB0127G | 132 | 2 | | ALL |
| 260R | 24 | PW | | KJ | 0-0 | 22-12-11 | D00413A | | A01 | | TB0127G | 131 | 2 | | ALL |
| 260Z | | | | KJ | 0-0 | 22-12-11 | D00413A | | DED | | GDY0006 | S.. | 2 | | ALL |
| 261B | 24 | PW | | KK | 5-0 | 22-12-21 | D00413D | | B01 | | TB0127G | 162 | 2 | | ALL |
| 261R | 24 | PW | | KK | 0-0 | 22-12-21 | D00413D | | A01 | | TB0127G | 161 | 2 | | ALL |
| 261Z | | | | KK | 0-0 | 22-12-21 | D00413D | | DED | | GDY0010 | S.. | 2 | | ALL |
| 262B | 24 | PW | | KL | 4-0 | 31-31-12 | D00413E | | B13 | | TB0127G | 143 | 2 | | ALL |
| 262R | 24 | PW | | KL | 0-0 | 31-31-12 | D00413E | | A13 | | TB0127G | 142 | 2 | | ALL |
| 262Z | | | | KL | 0-0 | 31-31-12 | D00413E | | DED | | GDY0007 | S.. | 2 | | ALL |
| 263B | 24 | PW | | KM | 4-0 | 34-22-38 | D00413A | | H06 | | TB0127F | C017 | 2 | | ALL |
| 263R | 24 | PW | | KM | 0-0 | 34-22-38 | D00413A | | G06 | | TB0127F | A017 | 2 | | ALL |
| 263Z | | | | KM | 0-0 | 34-22-38 | D00413A | | DED | | GDY0002 | S.. | 2 | | ALL |
| 264B | 24 | PW | | KN | 5-0 | 34-22-38 | D00413D | | H06 | | TB0127F | C054 | 2 | | ALL |
| 264R | 24 | PW | | KN | 0-0 | 34-22-38 | D00413D | | G06 | | TB0127F | A054 | 2 | | ALL |
| 264Z | | | | KN | 0-0 | 34-22-38 | D00413D | | DED | | GDY0009 | S.. | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1120

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1127 | 286T1127 | | | E1-4 SHELF EF1S SG,C (continued) | | | | | | | | | | | |
| 265B | 24 | PW | KO | | 4-0 | 34-22-39 | D00413A | K01 | | | TB0127F | C103 | 2 | | ALL |
| 265R | 24 | PW | KO | | 0-0 | 34-22-39 | D00413A | J01 | | | TB0127F | A103 | 2 | | ALL |
| 265Z | | | KO | | 0-0 | 34-22-39 | D00413A | DED | | | GDY0001 | S.. | 2 | | ALL |
| 266B | 24 | PW | KP | | 6-0 | 34-22-39 | D00413D | K01 | | | TB0127Y | C182 | BJ | | ALL |
| 266R | 24 | PW | KP | | 0-0 | 34-22-39 | D00413D | J01 | | | TB0127Y | A182 | BJ | | ALL |
| 266Z | | | KP | | 0-0 | 34-22-39 | D00413D | DED | | | GDY0012 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 266Z | | | KP | | 0-0 | 34-22-39 | D00413D | DED | | | GDY0011 | S.. | 2 | | 150-151 |
| 268B | 24 | PW | KR | | 4-0 | 34-22-33 | D00413A | D02 | | | TB0127G | 112 | 2 | | ALL |
| 268R | 24 | PW | KR | | 0-0 | 34-22-33 | D00413A | C02 | | | TB0127G | 111 | 2 | | ALL |
| 268Z | | | KR | | 0-0 | 34-22-33 | D00413A | DED | | | GDY0001 | S.. | 2 | | ALL |
| 269B | 24 | PW | KS | | 4-0 | 34-22-33 | D00413D | D02 | | | TB0127G | 108 | 2 | | ALL |
| 269R | 24 | PW | KS | | 0-0 | 34-22-33 | D00413D | C02 | | | TB0127G | 107 | 2 | | ALL |
| 269Z | | | KS | | 0-0 | 34-22-33 | D00413D | DED | | | GDY0001 | S.. | 2 | | ALL |
| 270B | 24 | PW | KT | | 4-0 | 34-22-38 | D02285 | B1 | | | TB0127X | B065 | BJ | | ALL |
| 270R | 24 | PW | KT | | 0-0 | 34-22-38 | D02285 | A1 | | | TB0127X | A065 | BJ | | ALL |
| 270Z | | | KT | | 0-0 | 34-22-38 | D02285 | DED | | | GDY0010 | S.. | 2 | | ALL |
| 271B | 24 | PW | KU | | 4-0 | 34-22-38 | D02285 | D1 | | | TB0127X | D065 | BJ | | ALL |
| 271R | 24 | PW | KU | | 0-0 | 34-22-38 | D02285 | C1 | | | TB0127X | C065 | BJ | | ALL |
| 271Z | | | KU | | 0-0 | 34-22-38 | D02285 | DED | | | GDY0010 | S.. | 2 | | ALL |
| 272B | 24 | PW | KV | | 4-0 | 34-22-38 | D02285 | B3 | | | TB0127X | B066 | BJ | | ALL |
| 272R | 24 | PW | KV | | 0-0 | 34-22-38 | D02285 | A3 | | | TB0127X | A066 | BJ | | ALL |
| 272Z | | | KV | | 0-0 | 34-22-38 | D02285 | DED | | | GDY0010 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 272Z | | | KV | | 0-0 | 34-22-38 | D02285 | DED | | | GDY0011 | S.. | 2 | | 150-151 |
| 273B | 24 | PW | KW | | 4-0 | 34-22-38 | D02285 | D3 | | | TB0127X | D066 | BJ | | ALL |
| 273R | 24 | PW | KW | | 0-0 | 34-22-38 | D02285 | C3 | | | TB0127X | C066 | BJ | | ALL |
| 273Z | | | KW | | 0-0 | 34-22-38 | D02285 | DED | | | GDY0010 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 273Z | | | KW | | 0-0 | 34-22-38 | D02285 | DED | | | GDY0011 | S.. | 2 | | 150-151 |
| 274B | 24 | PW | KX | | 4-0 | 34-22-38 | D02285 | D2 | | | TB0127Y | C181 | BJ | | ALL |
| 274R | 24 | PW | KX | | 0-0 | 34-22-38 | D02285 | C2 | | | TB0127Y | A181 | BJ | | ALL |
| 274Z | | | KX | | 0-0 | 34-22-38 | D02285 | DED | | | GDY0012 | S.. | 2 | | 050-099, 152-199, 275-299 |
| 274Z | | | KX | | 0-0 | 34-22-38 | D02285 | DED | | | GDY0011 | S.. | 2 | | 150-151 |
| 278B | 24 | PW | LC | | 4-0 | 34-45-14 | D00413A | K09 | | | TB0127F | C129 | 2 | | 050-099, 153-199, 277-299 |
| 278B | 24 | PW | LC | | 4-0 | 34-45-14 | D00413A | K09 | | | TB0127F | C136 | 2 | | 150-152 |

WIRE LIST

D280T132

91-21-11
Section W1120
Page 9
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1127 | 286T1127 | | | E1-4 SHELF EF1S SG,C (continued) | | | | | | | | | | | |
| 278R | 24 | PW | LC | 0-0 | 34-45-14 | D00413A | J09 | | | | TB0127F | A129 | 2 | | 050-099, 153-199, 277-299 |
| 278R | 24 | PW | LC | 0-0 | 34-45-14 | D00413A | J09 | | | | TB0127F | A136 | 2 | | 150-152 |
| 278Z | | | LC | 0-0 | 34-45-14 | D00413A | DED | | | | GDY0006 | S.. | 2 | | 050-099, 150-199, 277-299 |
| 279B | 24 | PW | LD | 4-0 | 34-45-14 | D00413D | K09 | | | | TB0127X | B012 | BJ | | 157, 167-199, 277-299 |
| 279R | 24 | PW | LD | 0-0 | 34-45-14 | D00413D | J09 | | | | TB0127X | A012 | BJ | | 157, 167-199, 277-299 |
| 279Z | | | LD | 0-0 | 34-45-14 | D00413D | DED | | | | GDY0002 | S.. | 2 | | 157, 167-199, 277-299 |
| 601 | 22 | PA | | 4-0 | 34-22-36 | D00413D | G12 | | | | TB0127F | A007 | 2 | | ALL |
| 604 | 22 | PA | | 3-0 | 34-22-36 | D00413B | G03 | | | | GDX0003 | S.. | # | | 050-099, 150-156, 162-166 |
| 604 | 22 | PA | | 3-0 | 34-22-36 | D00413B | G03 | | | | GDX0002 | S.. | # | | 157, 167-199, 277-299 |
| 605 | 22 | PA | | 3-0 | 34-22-36 | D00413B | G12 | | | | GDX0003 | S.. | # | | 050-099, 150-156, 162-166 |
| 605 | 22 | PA | | 3-0 | 34-22-36 | D00413B | G12 | | | | GDX0002 | S.. | # | | 157, 167-199, 277-299 |
| 606 | 22 | PA | | 3-0 | 34-22-36 | D00413B | H03 | | | | GDX0002 | S.. | # | | 153-154, 157, 167-199, 277-299 |
| 607 | 22 | PA | | 3-0 | 34-22-36 | D00413B | J04 | | | | GDX0002 | S.. | # | | 153-154, 157, 167-199, 277-299 |
| 608 | 22 | PA | | 3-0 | 34-22-36 | D00413A | B10 | | | | GDX0002 | S.. | # | | 153-154, 157, 167-199, 277-299 |
| 609 | 22 | PA | | 3-0 | 34-22-36 | D00413B | B02 | | | | GDX0002 | S.. | # | | 153-154 |
| 624 | 24 | PK | | 6-0 | 34-22-38 | D02285 | X2 | | | | TB0127Y | A119 | BJ | | ALL |
| 633 | 24 | PK | | 4-0 | 34-22-38 | D02285 | X1 | | | | TB0127F | A064 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1120

Page 10 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|-----|-----------------------------------|----------|---------|------|------|--------|--------|------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1130 | 286T1130 | | | | P40 APU REMOTE CONTROL PNL | | | | | | | | | | | |
| 001 | 18 | | UA | | 3-0 | 23-43-11 | D05938P | | 1 | | S00426 | 2 | J | | 050-099, 155-199, 275-278 | |
| 001 | 18 | | UA | | 4-0 | 23-43-11 | D05938J | | 1 | | S00426 | 2 | J | | 150-154 | |
| 001 | 18 | | UA | | 4-0 | 23-43-11 | D05938P | | 1 | | S00426 | 2 | J | | 280-299 | |
| 002 | 18 | | UA | | 3-0 | 23-43-11 | D05938P | | 2 | | S00426 | 1 | J | | 050-099, 155-199, 275-278 | |
| 002 | 18 | | UA | | 4-0 | 23-43-11 | D05938J | | 2 | | S00426 | 1 | J | | 150-154 | |
| 002 | 18 | | UA | | 4-0 | 23-43-11 | D05938P | | 2 | | S00426 | 1 | J | | 280-299 | |
| 003 | 18 | | UA | | 3-0 | 33-51-21 | D05938P | | 9 | | S00466 | 3 | L | | 050-099, 155-199, 275-278 | |
| 003 | 18 | | UA | | 3-0 | 33-51-21 | D05938J | | 9 | | S00466 | 3 | L | | 150-154 | |
| 003 | 18 | | UA | | 4-0 | 33-51-21 | D05938P | | 9 | | S00466 | 3 | L | | 280-299 | |
| 004 | 18 | | UA | | 3-0 | 33-51-21 | D05938P | | 10 | | S00466 | 1 | L | | 050-099, 155-199, 275-278 | |
| 004 | 18 | | UA | | 3-0 | 33-51-21 | D05938J | | 10 | | S00466 | 1 | L | | 150-154 | |
| 004 | 18 | | UA | | 4-0 | 33-51-21 | D05938P | | 10 | | S00466 | 1 | L | | 280-299 | |
| 005 | 18 | | UA | | 3-0 | 33-51-21 | D05938P | | 11 | | S00466 | 2 | L | | 050-099, 155-199, 275-278 | |
| 005 | 18 | | UA | | 3-0 | 33-51-21 | D05938J | | 11 | | S00466 | 2 | L | | 150-154 | |
| 005 | 18 | | UA | | 4-0 | 33-51-21 | D05938P | | 11 | | S00466 | 2 | L | | 280-299 | |
| 006 | 18 | | UA | | 3-0 | 33-31-11 | D05938P | | 12 | | S00324 | 2 | L | | 050-099, 155-199, 275-278 | |
| 006 | 18 | | UA | | 3-0 | 33-31-11 | D05938J | | 12 | | S00324 | 2 | L | | 150-154 | |
| 006 | 18 | | UA | | 4-0 | 33-31-11 | D05938P | | 12 | | S00324 | 2 | L | | 280-299 | |
| 007 | 18 | | UA | | 3-0 | 33-31-11 | D05938P | | 13 | | S00324 | 1 | L | | 050-099, 155-199, 275-278 | |
| 007 | 18 | | UA | | 3-0 | 33-31-11 | D05938J | | 13 | | S00324 | 1 | L | | 150-154 | |
| 007 | 18 | | UA | | 4-0 | 33-31-11 | D05938P | | 13 | | S00324 | 1 | L | | 280-299 | |
| A-A | | | | A | 0-0 | 23-41-11 | D05938P | | 4 | | D08543 | | RED | | 050-099, 155-199, 275-299 | |
| A-A | | | | A | 0-0 | 23-41-11 | D05938J | | 4 | | D08543 | | RED | | 150-154 | |
| A-B | | | | A | 0-0 | 23-41-11 | D05938P | | 3 | | D08543 | | BLU | | 050-099, 155-199, 275-299 | |
| A-B | | | | A | 0-0 | 23-41-11 | D05938J | | 3 | | D08543 | | BLU | | 150-154 | |
| A-C | | | | A | 0-0 | 23-41-11 | D05938P | | 5 | | D08543 | | BLK | | 050-099, 155-199, 275-299 | |
| A-C | | | | A | 0-0 | 23-41-11 | D05938J | | 5 | | D08543 | | BLK | | 150-154 | |
| A-D | | | | B | 0-0 | 23-51-11 | D05938P | | 7 | | D08545 | | RED | | 050-099, 155-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W1130

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|-------|------|---------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1130 | 286T1130 | | | | P40 APU REMOTE CONTROL PNL (continued) | | | | | | | | | | | |
| A-D | | | | B | 0-0 | 23-51-11 | D05938J | | | 7 | | | D08545 | RED | | 150-154 |
| A-E | | | | B | 0-0 | 23-51-11 | D05938P | | | 6 | | | D08545 | BLU | | 050-099, 155-199, 275-299 |
| A-E | | | | B | 0-0 | 23-51-11 | D05938J | | | 6 | | | D08545 | BLU | | 150-154 |
| A-F | | | | B | 0-0 | 23-51-11 | D05938P | | | 8 | | | D08545 | BLK | | 050-099, 155-199, 275-299 |
| A-F | | | | B | 0-0 | 23-51-11 | D05938J | | | 8 | | | D08545 | BLK | | 150-154 |
| W1131 | 286T1131 | | | | E2-1 SHELF | | | | | | | | | | | |
| 001 | 22 | | PA | | 3-0 | 22-22-21 | D00667B | | | E05 | | | D05035J | 4 | | ALL |
| 002 | 22 | | PA | | 3-0 | 22-21-21 | D05035J | | | 3 | | | D01261B | K07 | | ALL |
| 003 | 22 | | PA | | 3-0 | 22-21-21 | D05035J | | | 2 | | | D01261B | K08 | | ALL |
| 014 | 22 | | PQ | AN | 3-0 | 27-41-31 | D05035J | | | 26 | | | D00667A | B06 | | 050-099, 155-199, 275-299 |
| 014Z | | | | AN | 0-0 | 27-41-31 | D05035J | | | DED | | | D00667A | DED | | 050-099, 155-199, 275-299 |
| 015 | 22 | | PA | | 3-0 | 27-09-14 | D05035J | | | 11 | | | TB0141G | 149 2 | | ALL |
| 016 | 22 | | PA | | 4-0 | 27-09-14 | D01255B | | | K13 | | | TB0141G | 149 2 | | ALL |
| 017 | 22 | | PA | | 4-0 | 27-09-14 | D01265B | | | D14 | | | D05035J | 39 | | ALL |
| 018 | 22 | | PA | | 3-0 | 27-09-14 | D01261B | | | G10 | | | D05035J | 37 | | ALL |
| 019 | 22 | | PA | | 3-0 | 27-09-14 | D00667B | | | A15 | | | D05035J | 38 | | ALL |
| 020 | 22 | | PA | | 3-0 | 27-09-14 | D00835A | | | H14 | | | TB0141H | 147 2 | | ALL |
| 021 | 22 | | PA | | 4-0 | 27-09-14 | D00833A | | | H14 | | | TB0141H | 147 2 | | ALL |
| 022 | 22 | | PA | | 3-0 | 27-09-14 | D05035J | | | 36 | | | TB0141H | 147 2 | | ALL |
| 023 | 22 | | PA | | 4-0 | 27-09-14 | D00831A | | | H14 | | | TB0141H | 147 2 | | ALL |
| 024 | 22 | | PA | | 3-0 | 27-09-14 | D01257B | | | K13 | | | TB0141G | 149 2 | | ALL |
| 025 | 22 | | PQ | AY | 3-0 | 27-11-22 | D00667B | | | B01 | | | TB0141G | 49 2 | | ALL |
| 025Z | | | | AY | 0-0 | 27-11-22 | D00667B | | | DED | | | TB0141G | DED | | ALL |
| 026 | 22 | | PQ | BA | 3-0 | 27-11-22 | D00667B | | | A01 | | | TB0141G | 49 2 | | ALL |
| 026Z | | | | BA | 0-0 | 27-11-22 | D00667B | | | DED | | | TB0141G | DED | | ALL |
| 027 | 20 | | PQ | BB | 3-0 | 27-11-22 | D05035J | | | 1 | | | TB0141G | 49 2 | | ALL |
| 027Z | | | | BB | 0-0 | 27-11-22 | D05035J | | | DED | | | TB0141G | DED | | ALL |
| 028 | 22 | | PA | | 3-0 | 27-11-22 | D00667B | | | A04 | | | TB0141G | 50 2 | | ALL |
| 029 | 20 | | PA | | 3-0 | 27-11-22 | D05035J | | | 10 | | | TB0141G | 50 2 | | ALL |
| 030 | 20 | | PA | | 3-0 | 27-11-22 | D05035J | | | 12 | | | TB0141G | 50 2 | | ALL |
| 031 | 22 | | PA | | 3-0 | 27-11-22 | D00667B | | | A03 | | | TB0141G | 51 2 | | ALL |
| 032 | 20 | | PA | | 3-0 | 27-11-22 | D05035J | | | 7 | | | TB0141G | 51 2 | | ALL |
| 033 | 20 | | PA | | 3-0 | 27-11-22 | D05035J | | | 13 | | | TB0141G | 51 2 | | ALL |
| 034 | 22 | | PA | | 3-0 | 27-11-22 | D00667B | | | B13 | | | TB0141G | 52 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1130

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|-----|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1131 | 286T1131 | | | E2-1 SHELF (continued) | | | | | | | | | | | | |
| 035 | 22 | | PA | | 3-0 | 27-11-22 | D05035J | | | 8 | | | TB0141G | 52 | 2 | ALL |
| 036 | 22 | | PA | | 3-0 | 27-11-22 | D05035J | | | 16 | | | TB0141G | 52 | 2 | ALL |
| 037 | 22 | | PA | | 3-0 | 27-11-22 | D00667B | | | B15 | | | TB0141G | 53 | 2 | ALL |
| 038 | 22 | | PA | | 3-0 | 27-11-22 | D05035J | | | 9 | | | TB0141G | 53 | 2 | ALL |
| 039 | 22 | | PA | | 3-0 | 27-11-22 | D05035J | | | 17 | | | TB0141G | 53 | 2 | ALL |
| 040 | 22 | | PA | | 3-0 | 27-11-22 | D00667B | | | B12 | | | D05035J | 14 | | ALL |
| 041 | 22 | | PA | | 3-0 | 27-11-22 | D00667B | | | B14 | | | D05035J | 15 | | ALL |
| 042 | 22 | | PA | | 3-0 | 27-11-22 | D00667B | | | A11 | | | D05035J | 18 | | ALL |
| 043 | 22 | | PA | | 4-0 | 27-21-12 | D01265B | | | A14 | | | D05035J | 19 | | ALL |
| 044 | 22 | | PA | | 4-0 | 27-41-21 | D00667B | | | C11 | | | D05035J | 20 | | ALL |
| 045 | 22 | | PA | | 4-0 | 27-41-21 | D00667B | | | C13 | | | D05035J | 21 | | ALL |
| 046 | 22 | | PA | | 3-0 | 27-61-12 | D05035J | | | 22 | | | TB0141G | 150 | 2 | ALL |
| 047 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | H15 | | | TB0141G | 150 | 2 | ALL |
| 048 | 22 | | PA | | 4-0 | 27-61-12 | D00833A | | | H15 | | | TB0141G | 150 | 2 | ALL |
| 049 | 22 | | PA | | 4-0 | 27-61-12 | D00831A | | | H15 | | | TB0141G | 150 | 2 | ALL |
| 050 | 22 | | PA | | 3-0 | 27-61-12 | D00833A | | | C15 | | | D00831A | C14 | | ALL |
| 052 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | H13 | | | D05035J | 30 | | ALL |
| 053 | 22 | | PA | | 4-0 | 27-61-12 | D00833A | | | H13 | | | D05035J | 29 | | ALL |
| 054 | 22 | | PA | | 4-0 | 27-61-12 | D00831A | | | H13 | | | D05035J | 28 | | ALL |
| 059 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | G13 | | | D00833A | D13 | | ALL |
| 060 | 22 | | PA | | 4-0 | 27-61-12 | D00833A | | | F13 | | | D00835A | E13 | | ALL |
| 061 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | G14 | | | D00833A | D14 | | ALL |
| 062 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | E14 | | | D00833A | F14 | | ALL |
| 063 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | G15 | | | D00833A | E15 | | ALL |
| 064 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | D15 | | | D00833A | F15 | | ALL |
| 065 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | F13 | | | D00831A | E13 | | ALL |
| 066 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | D13 | | | D00831A | G13 | | ALL |
| 067 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | F14 | | | D00831A | E14 | | ALL |
| 068 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | D14 | | | D00831A | G14 | | ALL |
| 069 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | F15 | | | D00831A | D15 | | ALL |
| 070 | 22 | | PA | | 4-0 | 27-61-12 | D00835A | | | E15 | | | D00831A | G15 | | ALL |
| 071 | 22 | | PA | | 3-0 | 27-61-12 | D00833A | | | G13 | | | D00831A | D13 | | ALL |
| 072 | 22 | | PA | | 3-0 | 27-61-12 | D00833A | | | E13 | | | D00831A | F13 | | ALL |
| 073 | 22 | | PA | | 3-0 | 27-61-12 | D00833A | | | G14 | | | D00831A | D14 | | ALL |
| 074 | 22 | | PA | | 3-0 | 27-61-12 | D00833A | | | E14 | | | D00831A | F14 | | ALL |
| 075 | 22 | | PA | | 3-0 | 27-61-12 | D00833A | | | G15 | | | D00831A | E15 | | ALL |
| 076 | 22 | | PA | | 3-0 | 27-61-12 | D00833A | | | D15 | | | D00831A | F15 | | ALL |
| 077 | 22 | | PA | | 5-0 | 27-09-11 | D01257B | | | C10 | | | D01255B | A10 | | ALL |
| 078 | 22 | | PA | | 5-0 | 27-09-11 | D01257B | | | A10 | | | D01255B | C10 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1130
Page 3
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1131 | 286T1131 | | | E2-1 SHELF (continued) | | | | | | | | | | | | | |
| 092 | 22 | | PA | 4-0 | 27-61-12 | D00835A | | C15 | | | | | D00833A | B14 | | | ALL |
| 093 | 22 | | PA | 4-0 | 27-61-12 | D00835A | | B14 | | | | | D00831A | C15 | | | ALL |
| W1132 | 286T1132 | | | P40 APU REMOTE CONTROL PANEL | | | | | | | | | | | | | |
| 001R | 18 | | XG | 2-0 | 26-22-21 | D05936P | | 2 | | | | | SM00002 | | 9 | | 050-099, 155-199, 275-276 |
| 001R | 18 | | XG | 2-0 | 26-22-21 | D05936J | | 2 | | | | | SM00002 | | 9 | | 150-154 |
| 001R | 18 | | XG | 3-0 | 26-22-21 | D05936P | | 2 | | | | | SM00002 | | 9 | | 277-299 |
| 004R | 18 | | XG | 3-0 | 26-15-12 | SM00001 | | | 9 | | | | L00541 | GND | L | | ALL |
| 005R | 18 | | XG | 2-0 | 26-22-21 | D05936P | | 7 | | | | | SM00003 | | 9 | | 050-099, 155-199, 275-276 |
| 005R | 18 | | XG | 2-0 | 26-22-21 | D05936J | | 7 | | | | | SM00003 | | 9 | | 150-154 |
| 005R | 18 | | XG | 3-0 | 26-22-21 | D05936P | | 7 | | | | | SM00003 | | 9 | | 277-299 |
| 006R | 18 | | XG | 2-0 | 26-22-21 | L00543 | | 1 | \$ | | | | SM00003 | | 9 | | ALL |
| 007R | 18 | | XG | 3-0 | 26-22-21 | D05936P | | 11 | | | | | L00543 | 2 | \$ | | 050-099, 155-199, 275-278 |
| 007R | 18 | | XG | 3-0 | 26-22-21 | D05936J | | 11 | | | | | L00543 | 2 | \$ | | 150-154 |
| 007R | 18 | | XG | 4-0 | 26-22-21 | D05936P | | 11 | | | | | L00543 | 2 | \$ | | 280-299 |
| 008R | 18 | | XG | 2-0 | 26-22-21 | SM00003 | | | 9 | | | | L00542 | 3 | \$ | | ALL |
| 009R | 18 | | XG | 3-0 | 26-22-21 | L00543 | | 3 | \$ | | | | SM00001 | | 9 | | ALL |
| 010R | 18 | | XG | 3-0 | 26-22-21 | L00542 | | 1 | \$ | | | | SM00001 | | 9 | | ALL |
| 011R | 18 | | XG | 2-0 | 26-15-12 | D05936P | | 12 | | | | | SM00001 | | 9 | | 050-099, 155-199, 275-276 |
| 011R | 18 | | XG | 3-0 | 26-15-12 | D05936J | | 12 | | | | | SM00001 | | 9 | | 150-154 |
| 011R | 18 | | XG | 3-0 | 26-15-12 | D05936P | | 12 | | | | | SM00001 | | 9 | | 277-299 |
| 012R | 18 | | XG | 3-0 | 26-15-12 | D05936P | | 14 | | | | | B00122 | GND | N | | 050-099, 155-199, 275-299 |
| 012R | 18 | | XG | 3-0 | 26-15-12 | D05936J | | 14 | | | | | B00122 | GND | N | | 150-154 |
| 013R | 18 | | XG | 3-0 | 26-15-12 | B00122 | | B | M | | | | SM00001 | | 9 | | ALL |
| 014R | 18 | | XG | 3-0 | 26-15-12 | D05936P | | 13 | | | | | B00122 | A | M | | 050-099, 155-199, 275-299 |
| 014R | 18 | | XG | 3-0 | 26-15-12 | D05936J | | 13 | | | | | B00122 | A | M | | 150-154 |
| 015R | 18 | | XG | 3-0 | 26-22-21 | L00544 | | 3 | \$ | | | | SM00001 | | 9 | | 275-299 |
| 016R | 18 | | XG | 3-0 | 26-22-21 | SM00003 | | | 9 | | | | L00544 | 1 | \$ | | 275-299 |
| 017R | 18 | | XG | 3-0 | 26-22-21 | L00544 | | 2 | \$ | | | | D05936P | | 9 | | 275-278 |
| 017R | 18 | | XG | 4-0 | 26-22-21 | L00544 | | 2 | \$ | | | | D05936P | | 9 | | 280-299 |
| 018R | 18 | | XG | 2-0 | 26-22-21 | L00542 | | 2 | \$ | | | | SM00002 | | 9 | | ALL |
| 019R | 18 | | XG | 3-0 | 26-15-12 | SP02308 | | | 9 | | | | D05936P | | 8 | | 050-099, 155-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1130

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1132 | 286T1132 | | | P40 APU REMOTE CONTROL PANEL (continued) | | | | | | | | | | | |
| 019R | 18 | | XG | | 3-0 | 26-15-12 | SP02308 | | 9 | | D05936J | 8 | | | 150-154 |
| A-A | | | | | 0-0 | 26-22-21 | S00485 | | 1 | | SM00002 | | 9 | | ALL |
| A-B | | | | | 0-0 | 26-22-21 | S00485 | | 3 | | D05936P | 4 | | | 050-099, 155-199, 275-299 |
| A-B | | | | | 0-0 | 26-22-21 | S00485 | | 3 | | D05936J | 4 | | | 150-154 |
| A-C | | | | | 0-0 | 26-15-12 | L00541 | CTR | N | | SP02308 | | 9 | | ALL |
| A-D | | | | | 0-0 | 49-61-11 | D05936P | | 6 | | S00484 | 1 | | | 050-099, 155-199, 275-299 |
| A-D | | | | | 0-0 | 49-61-11 | D05936J | | 6 | | S00484 | 1 | | | 150-154 |
| A-E | | | | | 0-0 | 49-61-11 | SM00001 | | 9 | | S00484 | 3 | | | ALL |
| A-F | | | | | 0-0 | 26-22-21 | SM00002 | | 9 | | S00486 | 1 | | | 275-299 |
| A-G | | | | | 0-0 | 26-22-21 | S00486 | | 3 | | D05936P | 10 | | | 275-299 |
| A-H | | | | | 0-0 | SPARE | S00485 | | 2 | | S00485 | CAP | Y | | ALL |
| A-I | | | | | 0-0 | SPARE | S00485 | | 4 | | S00485 | CAP | Y | | ALL |
| A-J | | | | | 0-0 | SPARE | S00485 | | 5 | | S00485 | CAP | Y | | ALL |
| A-K | | | | | 0-0 | SPARE | S00485 | | 6 | | S00485 | CAP | Y | | ALL |
| A-L | | | | | 0-0 | SPARE | S00484 | | 2 | | S00484 | CAP | Y | | ALL |
| A-M | | | | | 0-0 | SPARE | S00484 | | 4 | | S00484 | CAP | Y | | ALL |
| A-N | | | | | 0-0 | SPARE | S00484 | | 5 | | S00484 | CAP | Y | | ALL |
| A-O | | | | | 0-0 | SPARE | S00484 | | 6 | | S00484 | CAP | Y | | ALL |
| A-P | | | | | 0-0 | SPARE | S00486 | | 2 | | S00486 | CAP | Y | | 275-299 |
| A-Q | | | | | 0-0 | SPARE | S00486 | | 4 | | S00486 | CAP | Y | | 275-299 |
| A-R | | | | | 0-0 | SPARE | S00486 | | 5 | | S00486 | CAP | Y | | 275-299 |
| A-S | | | | | 0-0 | SPARE | S00486 | | 6 | | S00486 | CAP | Y | | 275-299 |
| W1134 | 286T1134 | | | FWD CARGO COMPT LIGHTS AND DOOR CONTROL (P43 PNL) | | | | | | | | | | | |
| 001 | 22 | | PA | | 12-0 | 52-34-12 | D05886P | | 1 | | S00511 | 11 | C | * | ALL |
| 002 | 22 | | PA | | 12-0 | 52-34-12 | D05886P | | 2 | | S00511 | 10 | C | | ALL |
| 003 | 22 | | PA | | 12-0 | 52-34-12 | D05886P | | 3 | | S00511 | 9 | C | | ALL |
| 007 | 22 | | PA | | 12-0 | 52-34-12 | D05886P | | 7 | | L00597 | 2 | B | | ALL |
| 008 | 22 | | PA | | 12-0 | 52-34-12 | D05886P | | 6 | | L00599 | 2 | B | | ALL |
| 011 | 20 | | PA | | 12-0 | 33-31-61 | D05886P | | 11 | | S00515 | 3 | C | | ALL |
| 012 | 20 | | PA | | 12-0 | 33-31-61 | D05886P | | 12 | | S00515 | 2 | C | | ALL |
| 013 | 18 | | PA | | 12-0 | 33-37-11 | D05886P | | 13 | DL | S00513 | 2 | C | | ALL |
| 014 | 20 | | PA | | 12-0 | 33-37-11 | D05886P | | 14 | | S00513 | 1 | C | | 050-099 |
| 014 | 18 | | PA | | 12-0 | 33-37-11 | D05886P | | 14 | DL | S00513 | 1 | C | | 150-199, 275-299 |
| 015 | 18 | | PA | | 12-0 | 33-37-11 | D05886P | | 15 | DL | S00513 | 3 | C | | ALL |
| 021 | 22 | | PA | | 3-0 | 52-34-12 | S00511 | | 8 | C | S00511 | 11 | C | * | ALL |
| 023 | 20 | | PA | | 12-0 | 52-34-12 | L00599 | | 3 | B | GD04324 | D.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1130

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|--|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1134 | 286T1134 | | | FWD CARGO COMPT LIGHTS AND DOOR CONTROL (P43 PNL) (continued) | | | | | | | | | | | | |
| 023 | 20 | | PA | 9-0 | 52-34-12 | L00599 | 3 | B | * | GD04324 | D.. | 2 | | 150-199, 275-299 | | |
| 025 | 22 | | PA | 3-0 | 52-34-12 | L00599 | 3 | B | * | L00597 | 3 | B | | ALL | | |
| 031 | 22 | | PA | 12-0 | 52-34-12 | L00597 | 1 | B | * | D05886P | 4 | | | ALL | | |
| 032 | 22 | | PA | 3-0 | 52-34-12 | L00597 | 1 | B | * | L00599 | 1 | B | | ALL | | |
| W1136 | 286T1136 | | | AFT CARGO COMPT LIGHTS AND DOOR CONTROL(P44 PNL) | | | | | | | | | | | | |
| 001 | 22 | | PA | 10-8 | 52-35-12 | D05888P | 1 | | | S00512 | 11 | C | * | 050-099 | | |
| 001 | 22 | | PA | 13-1 | 52-35-12 | D05888P | 1 | | | S00512 | 11 | C | * | 150-199, 275-299 | | |
| 002 | 22 | | PA | 10-8 | 52-35-12 | D05888P | 2 | | | S00512 | 10 | C | | 050-099 | | |
| 002 | 22 | | PA | 13-1 | 52-35-12 | D05888P | 2 | | | S00512 | 10 | C | | 150-199, 275-299 | | |
| 003 | 22 | | PA | 10-7 | 52-35-12 | D05888P | 3 | | | S00512 | 9 | C | | 050-099 | | |
| 003 | 22 | | PA | 13-0 | 52-35-12 | D05888P | 3 | | | S00512 | 9 | C | | 150-199, 275-299 | | |
| 004 | 22 | | PA | 10-6 | 52-35-12 | D05888P | 4 | | | S00510 | 11 | C | * | 050-099 | | |
| 004 | 22 | | PA | 12-11 | 52-35-12 | D05888P | 4 | | | S00510 | 11 | C | * | 150-199, 275-299 | | |
| 005 | 22 | | PA | 10-6 | 52-35-12 | D05888P | 5 | | | S00510 | 10 | C | * | 050-099 | | |
| 005 | 22 | | PA | 12-11 | 52-35-12 | D05888P | 5 | | | S00510 | 10 | C | * | 150-199, 275-299 | | |
| 007 | 22 | | PA | 10-9 | 52-35-12 | D05888P | 7 | | | L00598 | 2 | B | | 050-099 | | |
| 007 | 22 | | PA | 13-2 | 52-35-12 | D05888P | 7 | | | L00598 | 2 | B | | 150-199, 275-299 | | |
| 008 | 22 | | PA | 10-9 | 52-35-12 | D05888P | 6 | | | L00600 | 2 | B | | 050-099 | | |
| 008 | 22 | | PA | 13-2 | 52-35-12 | D05888P | 6 | | | L00600 | 2 | B | | 150-199, 275-299 | | |
| 011 | 20 | | UA | 10-4 | 33-31-61 | D05888P | 11 | | | S00516 | 1 | C | | 050-099 | | |
| 011 | 20 | | UA | 12-9 | 33-31-61 | D05888P | 11 | | | S00516 | 1 | C | | 150-199, 275-299 | | |
| 012 | 20 | | UA | 10-4 | 33-31-61 | D05888P | 12 | | | S00516 | 2 | C | | 050-099 | | |
| 012 | 20 | | UA | 12-9 | 33-31-61 | D05888P | 12 | | | S00516 | 2 | C | | 150-199, 275-299 | | |
| 013 | 18 | | UA | 10-4 | 33-37-21 | D05888P | 13 | DL | | S00514 | 2 | C | | 050-099 | | |
| 013 | 16 | | UA | 12-9 | 33-37-21 | D05888P | 13 | FL | | S00514 | 2 | C | | 150-199, 275-299 | | |
| 014 | 20 | | UA | 10-4 | 33-37-21 | D05888P | 14 | | | S00514 | 1 | C | | 050-099 | | |
| 014 | 16 | | UA | 12-9 | 33-37-21 | D05888P | 14 | FL | | S00514 | 1 | C | | 150-199, 275-299 | | |
| 015 | 20 | | UA | 10-4 | 33-37-21 | D05888P | 15 | | | S00514 | 3 | C | | 050-099 | | |
| 015 | 16 | | UA | 12-9 | 33-37-21 | D05888P | 15 | FL | | S00514 | 3 | C | | 150-199, 275-299 | | |
| 021 | 22 | | PA | 1-6 | 52-35-12 | S00512 | 8 | C | | S00512 | 11 | C | * | ALL | | |
| 023 | 20 | | UA | 5-2 | 52-35-12 | L00600 | 3 | B | * | GD00330 | D.. | 2 | | 050-099 | | |
| 023 | 20 | | UA | 11-11 | 52-35-12 | L00600 | 3 | B | * | GD00330 | D.. | 2 | | 150-199, 275-299 | | |
| 025 | 22 | | PA | 1-6 | 52-35-12 | L00600 | 3 | B | * | L00598 | 3 | B | | ALL | | |
| 029 | 22 | | PA | 1-6 | 52-35-12 | S00510 | 9 | C | | S00510 | 10 | C | * | ALL | | |
| 030 | 22 | | PA | 1-6 | 52-35-12 | S00510 | 11 | C | * | S00510 | 8 | C | * | ALL | | |
| 031 | 22 | | PA | 1-7 | 52-35-12 | L00598 | 1 | B | * | S00510 | 8 | C | * | ALL | | |
| 032 | 22 | | PA | 1-6 | 52-35-12 | L00598 | 1 | B | * | L00600 | 1 | B | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W1130

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-----------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1138 | 286T1138 | | | CENTER PSU MOD | | | | | | | | | | | |
| 001 | 18 | | PA | | 3-0 | 33-24-13 | D05968J | | 1 | DK | SM00001 | | | S | 050-099, 276-299 |
| 001 | 18 | | PA | | 3-0 | 33-24-13 | D05968J | | 1 | DK | SM00046 | | | S | 150-199, 275 |
| 002 | 18 | | PA | | 3-0 | 33-24-13 | D05968J | | 2 | DK | SM00002 | | | S | 050-099, 276-299 |
| 002 | 18 | | PA | | 3-0 | 33-24-13 | D05968J | | 2 | DK | SM00047 | | | S | 150-199, 275 |
| 003 | 18 | | PA | | 7-0 | 33-24-13 | SM00001 | | | S | SM00003 | | | S | 050-099, 276-299 |
| 003 | 18 | | PA | | 7-0 | 33-24-13 | SM00048 | | | S | SM00046 | | | S | 150-199, 275 |
| 004 | 18 | | PA | | 7-0 | 33-24-13 | SM00002 | | | S | SM00004 | | | S | 050-099, 276-299 |
| 004 | 18 | | PA | | 7-0 | 33-24-13 | SM00049 | | | S | SM00047 | | | S | 150-199, 275 |
| 005 | 18 | | PA | | 6-0 | 33-24-13 | SM00003 | | | S | SM00005 | | | S | 050-099, 276-299 |
| 005 | 20 | | PA | | 3-0 | 33-24-13 | D02424 | | 3 | | SM00047 | | | S | 150-199, 275 |
| 006 | 18 | | PA | | 6-0 | 33-24-13 | SM00004 | | | S | SM00006 | | | S | 050-099, 276-299 |
| 006 | 20 | | PA | | 3-0 | 33-24-13 | D02424 | | 4 | | SM00046 | | | S | 150-199, 275 |
| 007 | 18 | | PA | | 4-0 | 33-24-13 | SM00005 | | | S | D05970P | 1 | DK | | 050-099, 276-299 |
| 007 | 20 | | PA | | 8-0 | 33-24-13 | D02424 | | 5 | | GD01916 | A.. | 2 | | 150-199 |
| 007 | 20 | | PA | | 4-0 | 33-24-13 | D02424 | | 5 | | GD00119 | A.. | 2 | | 275 |
| 008 | 18 | | PA | | 4-0 | 33-24-13 | SM00006 | | | S | D05970P | 2 | DK | | 050-099, 276-299 |
| 008 | 20 | | PA | | 4-0 | 33-24-13 | SM00046 | | | S | D03260 | 4 | | | 150-199, 275 |
| 009 | 20 | | PA | | 4-0 | 33-24-13 | SM00047 | | | S | D03260 | 3 | | | 150-199, 275 |
| 010 | 20 | | PA | | 5-0 | 33-24-13 | GD01916 | | A.. | 2 | D03260 | 5 | | | 150-199 |
| 010 | 20 | | PA | | 6-0 | 33-24-13 | GD01916 | | A.. | 2 | D03260 | 5 | | | 275 |
| 013 | 20 | | PA | | 3-0 | 33-24-13 | SM00048 | | | S | D03262 | 4 | | | 150-199, 275 |
| 014 | 20 | | PA | | 3-0 | 33-24-13 | SM00049 | | | S | D03262 | 3 | | | 150-199, 275 |
| 015 | 20 | | PA | | 5-0 | 33-24-13 | GD01916 | | A.. | 2 | D03262 | 5 | | | 150-199, 275 |
| 016 | 18 | | PA | | 7-0 | 33-24-13 | SM00048 | | | S | SM00052 | | | S | 150-199, 275 |
| 017 | 18 | | PA | | 7-0 | 33-24-13 | SM00049 | | | S | SM00053 | | | S | 150-199, 275 |
| 018 | 20 | | PA | | 4-0 | 33-24-13 | SM00048 | | | S | D03264 | 4 | | | 150-199, 275 |
| 019 | 20 | | PA | | 4-0 | 33-24-13 | SM00049 | | | S | D03264 | 3 | | | 150-199, 275 |
| 020 | 20 | | PA | | 4-0 | 33-24-13 | GD01918 | | A.. | 2 | D03264 | 5 | | | 150-199 |
| 020 | 20 | | PA | | 5-0 | 33-24-13 | GD01918 | | A.. | 2 | D03264 | 5 | | | 275 |
| 023 | 20 | | PA | | 4-0 | 33-24-13 | SM00052 | | | S | D03266 | 4 | | | 150-199 |
| 023 | 20 | | PA | | 3-0 | 33-24-13 | SM00052 | | | S | D03266 | 4 | | | 275 |
| 024 | 20 | | PA | | 4-0 | 33-24-13 | SM00053 | | | S | D03266 | 3 | | | 150-199 |
| 024 | 20 | | PA | | 3-0 | 33-24-13 | SM00053 | | | S | D03266 | 3 | | | 275 |
| 025 | 20 | | PA | | 6-0 | 33-24-13 | GD01920 | | A.. | 2 | D03266 | 5 | | | 150-199, 275 |
| 026 | 18 | | PA | | 3-0 | 33-24-13 | SM00052 | | | S | D05970P | 1 | DK | | 150-199 |
| 026 | 18 | | PA | | 4-0 | 33-24-13 | SM00052 | | | S | D05970P | 1 | DK | | 275 |
| 027 | 18 | | PA | | 3-0 | 33-24-13 | SM00053 | | | S | D05970P | 2 | DK | | 150-199 |
| 027 | 18 | | PA | | 4-0 | 33-24-13 | SM00053 | | | S | D05970P | 2 | DK | | 275 |
| 103 | 22 | | PA | | 3-0 | 33-24-13 | SM00002 | | | S | D02424 | 3 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1130

Page 7

Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1138 | 286T1138 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | | |
| 103 | 20 | | PA | 3-0 | 33-24-13 | D02424 | | 3 | | | | | SM00002 | | S | | 276-299 |
| 104 | 22 | | PA | 3-0 | 33-24-13 | SM00001 | | | S | | | | D02424 | 4 | | | 050-099 |
| 104 | 20 | | PA | 3-0 | 33-24-13 | D02424 | | 4 | | | | | SM00001 | | S | | 276-299 |
| 105 | 20 | | PA | 4-0 | 33-24-13 | GD00119 | | A.. | 2 | | | | D02424 | 5 | | | 050-099 |
| 105 | 20 | | PA | 4-0 | 33-24-13 | D02424 | | 5 | | | | | GD00119 | A.. | 2 | | 276-299 |
| 113 | 22 | | PA | 4-0 | 33-24-13 | SM00002 | | | S | | | | D03260 | 3 | | | 050-099 |
| 113 | 20 | | PA | 4-0 | 33-24-13 | D03260 | | 3 | | | | | SM00002 | | S | | 276-299 |
| 114 | 22 | | PA | 4-0 | 33-24-13 | SM00001 | | | S | | | | D03260 | 4 | | | 050-099 |
| 114 | 20 | | PA | 4-0 | 33-24-13 | D03260 | | 4 | | | | | SM00001 | | S | | 276-299 |
| 115 | 20 | | PA | 7-0 | 33-24-13 | GD01916 | | A.. | 2 | | | | D03260 | 5 | | | 050-099 |
| 115 | 20 | | PA | 7-0 | 33-24-13 | D03260 | | 5 | | | | | GD01916 | A.. | 2 | | 276-299 |
| 123 | 22 | | PA | 3-0 | 33-24-13 | SM00004 | | | S | | | | D03262 | 3 | | | 050-099 |
| 123 | 20 | | PA | 3-0 | 33-24-13 | D03262 | | 3 | | | | | SM00004 | | S | | 276-299 |
| 124 | 22 | | PA | 3-0 | 33-24-13 | SM00003 | | | S | | | | D03262 | 4 | | | 050-099 |
| 124 | 20 | | PA | 3-0 | 33-24-13 | D03262 | | 4 | | | | | SM00003 | | S | | 276-299 |
| 125 | 20 | | PA | 5-0 | 33-24-13 | GD01916 | | A.. | 2 | | | | D03262 | 5 | | | 050-099 |
| 125 | 20 | | PA | 5-0 | 33-24-13 | D03262 | | 5 | | | | | GD01916 | A.. | 2 | | 276-299 |
| 133 | 22 | | PA | 4-0 | 33-24-13 | SM00004 | | | S | | | | D03264 | 3 | | | 050-099 |
| 133 | 20 | | PA | 4-0 | 33-24-13 | D03264 | | 3 | | | | | SM00004 | | S | | 276-299 |
| 134 | 22 | | PA | 4-0 | 33-24-13 | SM00003 | | | S | | | | D03264 | 4 | | | 050-099 |
| 134 | 20 | | PA | 4-0 | 33-24-13 | D03264 | | 4 | | | | | SM00003 | | S | | 276-299 |
| 135 | 20 | | PA | 5-0 | 33-24-13 | GD01918 | | A.. | 2 | | | | D03264 | 5 | | | 050-099 |
| 135 | 20 | | PA | 5-0 | 33-24-13 | D03264 | | 5 | | | | | GD01918 | A.. | 2 | | 276-299 |
| 143 | 22 | | PA | 3-0 | 33-24-13 | SM00006 | | | S | | | | D03266 | 3 | | | 050-099 |
| 143 | 20 | | PA | 3-0 | 33-24-13 | D03266 | | 3 | | | | | SM00006 | | S | | 276-299 |
| 144 | 22 | | PA | 3-0 | 33-24-13 | SM00005 | | | S | | | | D03266 | 4 | | | 050-099 |
| 144 | 20 | | PA | 3-0 | 33-24-13 | D03266 | | 4 | | | | | SM00005 | | S | | 276-299 |
| 145 | 20 | | PA | 6-0 | 33-24-13 | GD01920 | | A.. | 2 | | | | D03266 | 5 | | | 050-099 |
| 145 | 20 | | PA | 6-0 | 33-24-13 | D03266 | | 5 | | | | | GD01920 | A.. | 2 | | 276-299 |
| 201B | 22 | | PB IA | 3-0 | 23-31-16 | D05968J | | 3 | | | | | SM00102 | | S | | 050-099, 276-299 |
| 201B | 22 | | PB A | 3-0 | 23-31-16 | D05968J | | 3 | | | | | SM00002 | | S | | 150-199, 275 |
| 201R | 22 | | PB IA | 0-0 | 23-31-16 | D05968J | | 4 | | | | | SM00101 | | S | | 050-099, 276-299 |
| 201R | 22 | | PB A | 0-0 | 23-31-16 | D05968J | | 4 | | | | | SM00001 | | S | | 150-199, 275 |
| 202B | 22 | | PB IB | 3-0 | 23-31-16 | SM00102 | | | S | | | | D02424 | 2 | | | 050-099 |
| 202B | 22 | | PB B | 6-0 | 23-31-16 | D03260 | | 2 | | | | | SM00004 | | S | | 150-199 |
| 202B | 22 | | PB B | 4-0 | 23-31-16 | D03260 | | 2 | | | | | SM00002 | | S | | 275 |
| 202B | 22 | | PB IB | 3-0 | 23-31-16 | D02424 | | 2 | | | | | SM00102 | | S | | 276-299 |
| 202R | 22 | | PB IB | 0-0 | 23-31-16 | SM00101 | | | S | | | | D02424 | 1 | | | 050-099 |
| 202R | 22 | | PB B | 0-0 | 23-31-16 | D03260 | | 1 | | | | | SM00003 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1130

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | |
|--------------|-----------------|----|-------|-----------------------------------|------|----------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1138 | 286T1138 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | | | | |
| 202R | 22 | PB | B | | 0-0 | 23-31-16 | D03260 | | 1 | | | | | | SM00001 | | S | | 275 |
| 202R | 22 | PB | IB | | 0-0 | 23-31-16 | D02424 | | 1 | | | | | | SM00101 | | S | | 276-299 |
| 203B | 22 | PB | IC | | 7-0 | 23-31-16 | SM00102 | | | S | | | | | SM00104 | | S | | 050-099, 276-299 |
| 203R | 22 | PB | IC | | 0-0 | 23-31-16 | SM00101 | | | S | | | | | SM00103 | | S | | 050-099, 276-299 |
| 204B | 22 | PB | ID | | 4-0 | 23-31-16 | SM00102 | | | S | | | | | D03260 | | 2 | | 050-099 |
| 204B | 22 | PB | D | | 3-0 | 23-31-16 | D03262 | | 2 | | | | | | SM00004 | | S | | 150-199, 275 |
| 204B | 22 | PB | ID | | 4-0 | 23-31-16 | D03260 | | 2 | | | | | | SM00102 | | S | | 276-299 |
| 204R | 22 | PB | ID | | 0-0 | 23-31-16 | SM00101 | | | S | | | | | D03260 | | 1 | | 050-099 |
| 204R | 22 | PB | D | | 0-0 | 23-31-16 | D03262 | | 1 | | | | | | SM00003 | | S | | 150-199, 275 |
| 204R | 22 | PB | ID | | 0-0 | 23-31-16 | D03260 | | 1 | | | | | | SM00101 | | S | | 276-299 |
| 205B | 22 | PB | IE | | 6-0 | 23-31-16 | SM00104 | | | S | | | | | SM00106 | | S | | 050-099 |
| 205B | 22 | PB | E | | 7-0 | 23-31-16 | SM00004 | | | S | | | | | SM00008 | | S | | 150-199, 275 |
| 205B | 22 | PB | IE | | 7-0 | 23-31-16 | SM00104 | | | S | | | | | SM00106 | | S | | 276-299 |
| 205R | 22 | PB | IE | | 0-0 | 23-31-16 | SM00103 | | | S | | | | | SM00105 | | S | | 050-099, 276-299 |
| 205R | 22 | PB | E | | 0-0 | 23-31-16 | SM00003 | | | S | | | | | SM00007 | | S | | 150-199, 275 |
| 206B | 22 | PB | IF | | 3-0 | 23-31-16 | SM00104 | | | S | | | | | D03262 | | 2 | | 050-099 |
| 206B | 22 | PB | F | | 6-0 | 23-31-16 | D03264 | | 2 | | | | | | SM00008 | | S | | 150-199 |
| 206B | 22 | PB | F | | 4-0 | 23-31-16 | D03264 | | 2 | | | | | | SM00004 | | S | | 275 |
| 206B | 22 | PB | IF | | 3-0 | 23-31-16 | D03262 | | 2 | | | | | | SM00104 | | S | | 276-299 |
| 206R | 22 | PB | IF | | 0-0 | 23-31-16 | SM00103 | | | S | | | | | D03262 | | 1 | | 050-099 |
| 206R | 22 | PB | F | | 0-0 | 23-31-16 | D03264 | | 1 | | | | | | SM00007 | | S | | 150-199 |
| 206R | 22 | PB | F | | 0-0 | 23-31-16 | D03264 | | 1 | | | | | | SM00003 | | S | | 275 |
| 206R | 22 | PB | IF | | 0-0 | 23-31-16 | D03262 | | 1 | | | | | | SM00103 | | S | | 276-299 |
| 207B | 22 | PB | IG | | 4-0 | 23-31-16 | SM00106 | | | S | | | | | D05970P | | 3 | | 050-099, 276-299 |
| 207R | 22 | PB | IG | | 0-0 | 23-31-16 | SM00105 | | | S | | | | | D05970P | | 4 | | 050-099, 276-299 |
| 208B | 22 | PB | IH | | 4-0 | 23-31-16 | SM00104 | | | S | | | | | D03264 | | 2 | | 050-099 |
| 208B | 22 | PB | H | | 4-0 | 23-31-16 | D03266 | | 2 | | | | | | SM00008 | | S | | 150-199 |
| 208B | 22 | PB | H | | 3-0 | 23-31-16 | D03266 | | 2 | | | | | | SM00008 | | S | | 275 |
| 208B | 22 | PB | IH | | 4-0 | 23-31-16 | D03264 | | 2 | | | | | | SM00104 | | S | | 276-299 |
| 208R | 22 | PB | IH | | 0-0 | 23-31-16 | SM00103 | | | S | | | | | D03264 | | 1 | | 050-099 |
| 208R | 22 | PB | H | | 0-0 | 23-31-16 | D03266 | | 1 | | | | | | SM00007 | | S | | 150-199, 275 |
| 208R | 22 | PB | IH | | 0-0 | 23-31-16 | D03264 | | 1 | | | | | | SM00103 | | S | | 276-299 |
| 209B | 22 | PB | I | | 3-0 | 23-31-16 | D05970P | | 3 | | | | | | SM00008 | | S | | 150-199 |
| 209B | 22 | PB | I | | 4-0 | 23-31-16 | D05970P | | 3 | | | | | | SM00008 | | S | | 275 |
| 209R | 22 | PB | I | | 0-0 | 23-31-16 | D05970P | | 4 | | | | | | SM00007 | | S | | 150-199, 275 |
| 210B | 22 | PB | IJ | | 3-0 | 23-31-16 | SM00106 | | | S | | | | | D03266 | | 2 | | 050-099 |
| 210B | 22 | PB | IJ | | 3-0 | 23-31-16 | D03266 | | 2 | | | | | | SM00106 | | S | | 276-299 |
| 210R | 22 | PB | IJ | | 0-0 | 23-31-16 | SM00105 | | | S | | | | | D03266 | | 1 | | 050-099 |
| 210R | 22 | PB | IJ | | 0-0 | 23-31-16 | D03266 | | 1 | | | | | | SM00105 | | S | | 276-299 |

WIRE LIST

D280T132

91-21-11

Section W1130

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1138 | 286T1138 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | | |
| 211B | 22 | PB | AA | 3-0 | 23-31-16 | D05968J | | 5 | | | | | SM00102 | | S | | 150-199 |
| 211R | 22 | PB | AA | 0-0 | 23-31-16 | D05968J | | 6 | | | | | SM00101 | | S | | 150-199 |
| 212B | 22 | PB | AB | 6-0 | 23-31-16 | D03260 | | 7 | | | | | SM00104 | | S | | 150-199 |
| 212R | 22 | PB | AB | 0-0 | 23-31-16 | D03260 | | 6 | | | | | SM00103 | | S | | 150-199 |
| 214B | 22 | PB | AD | 3-0 | 23-31-16 | D03262 | | 7 | | | | | SM00104 | | S | | 150-199 |
| 214R | 22 | PB | AD | 0-0 | 23-31-16 | D03262 | | 6 | | | | | SM00103 | | S | | 150-199 |
| 215B | 22 | PB | AE | 7-0 | 23-31-16 | SM00104 | | | | S | | | SM00108 | | S | | 150-199 |
| 215R | 22 | PB | AE | 0-0 | 23-31-16 | SM00103 | | | | S | | | SM00107 | | S | | 150-199 |
| 216B | 22 | PB | FA | 6-0 | 23-31-16 | D03264 | | 7 | | | | | SM00108 | | S | | 150-199 |
| 216R | 22 | PB | FA | 0-0 | 23-31-16 | D03264 | | 6 | | | | | SM00107 | | S | | 150-199 |
| 218B | 22 | PB | AH | 4-0 | 23-31-16 | D03266 | | 7 | | | | | SM00108 | | S | | 150-199 |
| 218R | 22 | PB | AH | 0-0 | 23-31-16 | D03266 | | 6 | | | | | SM00107 | | S | | 150-199 |
| 219B | 22 | PB | AI | 3-0 | 23-31-16 | D05970P | | 5 | | | | | SM00108 | | S | | 150-199 |
| 219R | 22 | PB | AI | 0-0 | 23-31-16 | D05970P | | 6 | | | | | SM00107 | | S | | 150-199 |
| 246B | 22 | PB | J | 3-0 | 23-31-16 | D02424 | | 2 | | | | | SM00002 | | S | | 150-199, 275 |
| 246R | 22 | PB | J | 0-0 | 23-31-16 | D02424 | | 1 | | | | | SM00001 | | S | | 150-199, 275 |
| 247B | 22 | PB | K | 7-0 | 23-31-16 | SM00004 | | | | S | | | SM00002 | | S | | 150-199, 275 |
| 247R | 22 | PB | K | 0-0 | 23-31-16 | SM00003 | | | | S | | | SM00001 | | S | | 150-199, 275 |
| 251B | 22 | PB | KA | 3-0 | 23-31-16 | D05968J | | 5 | | | | | SM00202 | | S | | 050-099 |
| 251R | 22 | PB | KA | 0-0 | 23-31-16 | D05968J | | 6 | | | | | SM00201 | | S | | 050-099 |
| 252B | 22 | PB | KB | 3-0 | 23-31-16 | D02424 | | 7 | | | | | SM00202 | | S | | 050-099 |
| 252R | 22 | PB | KB | 0-0 | 23-31-16 | D02424 | | 6 | | | | | SM00201 | | S | | 050-099 |
| 253B | 22 | PB | KC | 7-0 | 23-31-16 | SM00202 | | | | S | | | SM00204 | | S | | 050-099 |
| 253R | 22 | PB | KC | 0-0 | 23-31-16 | SM00201 | | | | S | | | SM00203 | | S | | 050-099 |
| 254B | 22 | PB | KD | 4-0 | 23-31-16 | D03260 | | 7 | | | | | SM00202 | | S | | 050-099 |
| 254R | 22 | PB | KD | 0-0 | 23-31-16 | D03260 | | 6 | | | | | SM00201 | | S | | 050-099 |
| 255B | 22 | PB | KE | 6-0 | 23-31-16 | SM00204 | | | | S | | | SM00206 | | S | | 050-099 |
| 255R | 22 | PB | KE | 0-0 | 23-31-16 | SM00203 | | | | S | | | SM00205 | | S | | 050-099 |
| 256B | 22 | PB | KF | 3-0 | 23-31-16 | D03262 | | 7 | | | | | SM00204 | | S | | 050-099 |
| 256B | 22 | PB | AJ | 3-0 | 23-31-16 | D02424 | | 7 | | | | | SM00102 | | S | | 150-199 |
| 256R | 22 | PB | KF | 0-0 | 23-31-16 | D03262 | | 6 | | | | | SM00203 | | S | | 050-099 |
| 256R | 22 | PB | AJ | 0-0 | 23-31-16 | D02424 | | 6 | | | | | SM00101 | | S | | 150-199 |
| 257B | 22 | PB | KG | 4-0 | 23-31-16 | SM00206 | | | | S | | | D05970P | 5 | | | 050-099 |
| 257B | 22 | PB | AK | 7-0 | 23-31-16 | SM00104 | | | | S | | | SM00102 | | S | | 150-199 |
| 257R | 22 | PB | KG | 0-0 | 23-31-16 | SM00205 | | | | S | | | D05970P | 6 | | | 050-099 |
| 257R | 22 | PB | AK | 0-0 | 23-31-16 | SM00103 | | | | S | | | SM00101 | | S | | 150-199 |
| 258B | 22 | PB | KH | 4-0 | 23-31-16 | D03264 | | 7 | | | | | SM00204 | | S | | 050-099 |
| 258R | 22 | PB | KH | 0-0 | 23-31-16 | D03264 | | 6 | | | | | SM00203 | | S | | 050-099 |
| 260B | 22 | PB | KJ | 3-0 | 23-31-16 | D03266 | | 7 | | | | | SM00206 | | S | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1130

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|-----------------------------------|-------|----------|-------------|------|------|-----------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1138 | 286T1138 | | | CENTER PSU MOD (continued) | | | | | | | | | | | |
| 260R | 22 | PB | KJ | | 0-0 | 23-31-16 | D03266 | | 6 | | SM00205 | | S | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W1130
Page 11 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|----|-----------------|----|-----|-------------|-----------------------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1140 | | 286T1140 | | | | CENTER PSU MOD | | | | | | | | | | |
| 001 | 18 | PA | | | 3-0 | 33-24-13 | D05970J | 1 | DL | | SM00001 | | S | | 050-099, 276-299 | |
| 001 | 18 | PA | | | 3-0 | 33-24-13 | D05970J | 1 | DL | | SM00054 | | S | | 150-199, 275 | |
| 002 | 18 | PA | | | 3-0 | 33-24-13 | D05970J | 2 | DL | | SM00002 | | S | | 050-099, 276-299 | |
| 002 | 18 | PA | | | 3-0 | 33-24-13 | D05970J | 2 | DL | | SM00055 | | S | | 150-199, 275 | |
| 003 | 18 | PA | | | 7-0 | 33-24-13 | SM00001 | | S | | SM00003 | | S | | 050-099, 276-299 | |
| 003 | 20 | PA | | | 3-0 | 33-24-13 | D03268 | 3 | | | SM00055 | | S | | 150-199, 275 | |
| 004 | 18 | PA | | | 7-0 | 33-24-13 | SM00002 | | S | | SM00004 | | S | | 050-099, 276-299 | |
| 004 | 20 | PA | | | 3-0 | 33-24-13 | D03268 | 4 | | | SM00054 | | S | | 150-199, 275 | |
| 005 | 18 | PA | | | 6-0 | 33-24-13 | SM00003 | | S | | SM00005 | | S | | 050-099, 276-299 | |
| 005 | 20 | PA | | | 8-0 | 33-24-13 | D03268 | 5 | | | GD01924 | A.. | 2 | | 150-199, 275 | |
| 006 | 18 | PA | | | 6-0 | 33-24-13 | SM00004 | | S | | SM00006 | | S | | 050-099, 276-299 | |
| 006 | 18 | PA | | | 7-0 | 33-24-13 | SM00059 | | S | | SM00055 | | S | | 150-199, 275 | |
| 007 | 18 | PA | | | 4-0 | 33-24-13 | SM00005 | | S | | D05972P | 1 | DK | | 050-099, 276-299 | |
| 007 | 18 | PA | | | 7-0 | 33-24-13 | SM00058 | | S | | SM00054 | | S | | 150-199, 275 | |
| 008 | 18 | PA | | | 4-0 | 33-24-13 | SM00006 | | S | | D05972P | 2 | DK | | 050-099, 276-299 | |
| 008 | 20 | PA | | | 4-0 | 33-24-13 | SM00055 | | S | | D03270 | 3 | | | 150-199, 275 | |
| 009 | 20 | PA | | | 4-0 | 33-24-13 | SM00054 | | S | | D03270 | 4 | | | 150-199, 275 | |
| 010 | 20 | PA | | | 6-0 | 33-24-13 | GD01924 | A.. | 2 | | D03270 | 5 | | | 150-199, 275 | |
| 013 | 20 | PA | | | 3-0 | 33-24-13 | SM00059 | | S | | D03272 | 3 | | | 150-199, 275 | |
| 014 | 20 | PA | | | 3-0 | 33-24-13 | SM00058 | | S | | D03272 | 4 | | | 150-199, 275 | |
| 015 | 20 | PA | | | 5-0 | 33-24-13 | GD01924 | A.. | 2 | | D03272 | 5 | | | 150-199, 275 | |
| 016 | 18 | PA | | | 7-0 | 33-24-13 | SM00059 | | S | | SM00063 | | S | | 150-199, 275 | |
| 017 | 18 | PA | | | 7-0 | 33-24-13 | SM00058 | | S | | SM00062 | | S | | 150-199 | |
| 017 | 18 | PA | | | 6-0 | 33-24-13 | SM00058 | | S | | SM00062 | | S | | 275 | |
| 018 | 20 | PA | | | 4-0 | 33-24-13 | SM00059 | | S | | D03274 | 3 | | | 150-199, 275 | |
| 019 | 20 | PA | | | 4-0 | 33-24-13 | SM00058 | | S | | D03274 | 4 | | | 150-199, 275 | |
| 020 | 20 | PA | | | 8-0 | 33-24-13 | GD01924 | A.. | 2 | | D03274 | 5 | | | 150-199, 275 | |
| 023 | 20 | PA | | | 3-0 | 33-24-13 | D03276 | 4 | | | SM00062 | | S | | 150-199, 275 | |
| 024 | 20 | PA | | | 3-0 | 33-24-13 | D03276 | 3 | | | SM00063 | | S | | 150-199, 275 | |
| 025 | 20 | PA | | | 6-0 | 33-24-13 | D03276 | 5 | | | GD01930 | A.. | 2 | | 150-199 | |
| 025 | 20 | PA | | | 5-0 | 33-24-13 | D03276 | 5 | | | GD01930 | A.. | 2 | | 275 | |
| 026 | 18 | PA | | | 3-0 | 33-24-13 | D05972P | 1 | DK | | SM00062 | | S | | 150-199 | |
| 026 | 18 | PA | | | 4-0 | 33-24-13 | D05972P | 1 | DK | | SM00062 | | S | | 275 | |
| 027 | 18 | PA | | | 3-0 | 33-24-13 | D05972P | 2 | DK | | SM00063 | | S | | 150-199 | |
| 027 | 18 | PA | | | 4-0 | 33-24-13 | D05972P | 2 | DK | | SM00063 | | S | | 275 | |
| 103 | 22 | PA | | | 3-0 | 33-24-13 | SM00002 | | S | | D03268 | 3 | | | 050-099 | |
| 103 | 20 | PA | | | 3-0 | 33-24-13 | D03268 | 3 | | | SM00002 | | S | | 276-299 | |
| 104 | 22 | PA | | | 3-0 | 33-24-13 | SM00001 | | S | | D03268 | 4 | | | 050-099 | |
| 104 | 20 | PA | | | 3-0 | 33-24-13 | D03268 | 4 | | | SM00001 | | S | | 276-299 | |

WIRE LIST

D280T132

91-21-11

Section W1140

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1140 | 286T1140 | | | CENTER PSU MOD (continued) | | | | | | | | | | | |
| 105 | 20 | | PA | | 8-0 | 33-24-13 | D03268 | | 5 | | GD01924 | A.. | 2 | | 050-099, 276-299 |
| 113 | 22 | | PA | | 4-0 | 33-24-13 | SM00002 | | | S | D03270 | | 3 | | 050-099 |
| 113 | 20 | | PA | | 4-0 | 33-24-13 | D03270 | | 3 | | SM00002 | | | S | 276-299 |
| 114 | 22 | | PA | | 4-0 | 33-24-13 | SM00001 | | | S | D03270 | | 4 | | 050-099 |
| 114 | 20 | | PA | | 4-0 | 33-24-13 | D03270 | | 4 | | SM00001 | | | S | 276-299 |
| 115 | 20 | | PA | | 6-0 | 33-24-13 | GD01924 | A.. | 2 | | D03270 | | 5 | | 050-099 |
| 115 | 20 | | PA | | 6-0 | 33-24-13 | D03270 | | 5 | | GD01924 | A.. | 2 | | 276-299 |
| 123 | 22 | | PA | | 3-0 | 33-24-13 | SM00004 | | | S | D03272 | | 3 | | 050-099 |
| 123 | 20 | | PA | | 3-0 | 33-24-13 | D03272 | | 3 | | SM00004 | | | S | 276-299 |
| 124 | 22 | | PA | | 3-0 | 33-24-13 | SM00003 | | | S | D03272 | | 4 | | 050-099 |
| 124 | 20 | | PA | | 3-0 | 33-24-13 | D03272 | | 4 | | SM00003 | | | S | 276-299 |
| 125 | 20 | | PA | | 5-0 | 33-24-13 | GD01924 | A.. | 2 | | D03272 | | 5 | | 050-099 |
| 125 | 20 | | PA | | 5-0 | 33-24-13 | D03272 | | 5 | | GD01924 | A.. | 2 | | 276-299 |
| 133 | 22 | | PA | | 4-0 | 33-24-13 | SM00004 | | | S | D03274 | | 3 | | 050-099 |
| 133 | 20 | | PA | | 4-0 | 33-24-13 | D03274 | | 3 | | SM00004 | | | S | 276-299 |
| 134 | 22 | | PA | | 4-0 | 33-24-13 | SM00003 | | | S | D03274 | | 4 | | 050-099 |
| 134 | 20 | | PA | | 4-0 | 33-24-13 | D03274 | | 4 | | SM00003 | | | S | 276-299 |
| 135 | 20 | | PA | | 8-0 | 33-24-13 | GD01924 | A.. | 2 | | D03274 | | 5 | | 050-099 |
| 135 | 20 | | PA | | 8-0 | 33-24-13 | D03274 | | 5 | | GD01924 | A.. | 2 | | 276-299 |
| 143 | 22 | | PA | | 3-0 | 33-24-13 | SM00006 | | | S | D03276 | | 3 | | 050-099 |
| 143 | 20 | | PA | | 3-0 | 33-24-13 | D03276 | | 3 | | SM00006 | | | S | 276-299 |
| 144 | 22 | | PA | | 3-0 | 33-24-13 | D03276 | | 4 | | SM00005 | | | S | 050-099 |
| 144 | 20 | | PA | | 3-0 | 33-24-13 | D03276 | | 4 | | SM00005 | | | S | 276-299 |
| 145 | 20 | | PA | | 6-0 | 33-24-13 | D03276 | | 5 | | GD01930 | A.. | 2 | | 050-099, 276-299 |
| 201B | 22 | | PB | IA | 3-0 | 23-31-16 | D05970J | | 3 | | SM00102 | | | S | 050-099, 276-299 |
| 201B | 22 | | PB | A | 3-0 | 23-31-16 | D05970J | | 3 | | SM00010 | | | S | 150-199, 275 |
| 201R | 22 | | PB | IA | 0-0 | 23-31-16 | D05970J | | 4 | | SM00101 | | | S | 050-099, 276-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-16 | D05970J | | 4 | | SM00009 | | | S | 150-199, 275 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-16 | SM00102 | | | S | D03268 | | 2 | | 050-099 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-16 | D03268 | | 2 | | SM00102 | | | S | 276-299 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-16 | SM00101 | | | S | D03268 | | 1 | | 050-099 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-16 | D03268 | | 1 | | SM00101 | | | S | 276-299 |
| 203B | 22 | | PB | IC | 7-0 | 23-31-16 | SM00102 | | | S | SM00104 | | | S | 050-099, 276-299 |
| 203R | 22 | | PB | IC | 0-0 | 23-31-16 | SM00101 | | | S | SM00103 | | | S | 050-099, 276-299 |
| 204B | 22 | | PB | ID | 4-0 | 23-31-16 | SM00102 | | | S | D03270 | | 2 | | 050-099 |
| 204B | 22 | | PB | ID | 4-0 | 23-31-16 | D03270 | | 2 | | SM00102 | | | S | 276-299 |
| 204R | 22 | | PB | ID | 0-0 | 23-31-16 | SM00101 | | | S | D03270 | | 1 | | 050-099 |
| 204R | 22 | | PB | ID | 0-0 | 23-31-16 | D03270 | | 1 | | SM00101 | | | S | 276-299 |
| 205B | 22 | | PB | IE | 6-0 | 23-31-16 | SM00104 | | | S | SM00106 | | | S | 050-099, 276-299 |

WIRE LIST

D280T132

91-21-11

Section W1140

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1140 | 286T1140 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | | |
| 205R | 22 | PB | IE | 0-0 | 23-31-16 | SM00103 | | | | | | | | | | | 050-099, 276-299 |
| 206B | 22 | PB | IF | 3-0 | 23-31-16 | SM00104 | | | | | | | | | | | 050-099 |
| 206B | 22 | PB | IF | 3-0 | 23-31-16 | D03272 | | 2 | | | | | | | | | 276-299 |
| 206R | 22 | PB | IF | 0-0 | 23-31-16 | SM00103 | | | | | | | | | | | 050-099 |
| 206R | 22 | PB | IF | 0-0 | 23-31-16 | D03272 | | 1 | | | | | | | | | 276-299 |
| 207B | 22 | PB | IG | 4-0 | 23-31-16 | SM00106 | | | | | | | | | | | 050-099, 276-299 |
| 207R | 22 | PB | IG | 0-0 | 23-31-16 | SM00105 | | | | | | | | | | | 050-099, 276-299 |
| 208B | 22 | PB | IH | 4-0 | 23-31-16 | SM00104 | | | | | | | | | | | 050-099 |
| 208B | 22 | PB | IH | 4-0 | 23-31-16 | D03274 | | 2 | | | | | | | | | 276-299 |
| 208R | 22 | PB | IH | 0-0 | 23-31-16 | SM00103 | | | | | | | | | | | 050-099 |
| 208R | 22 | PB | IH | 0-0 | 23-31-16 | D03274 | | 1 | | | | | | | | | 276-299 |
| 210B | 22 | PB | IJ | 3-0 | 23-31-16 | SM00106 | | | | | | | | | | | 050-099 |
| 210B | 22 | PB | IJ | 3-0 | 23-31-16 | D03276 | | 2 | | | | | | | | | 050-099 |
| 210B | 22 | PB | B | 3-0 | 23-31-16 | D03268 | | 2 | | | | | | | | | 150-199, 275 |
| 210B | 22 | PB | IJ | 3-0 | 23-31-16 | D03276 | | 2 | | | | | | | | | 276-299 |
| 210R | 22 | PB | IJ | 0-0 | 23-31-16 | SM00105 | | | | | | | | | | | 050-099 |
| 210R | 22 | PB | B | 0-0 | 23-31-16 | D03268 | | 1 | | | | | | | | | 150-199, 275 |
| 210R | 22 | PB | IJ | 0-0 | 23-31-16 | D03276 | | 1 | | | | | | | | | 276-299 |
| 211B | 22 | PB | C | 7-0 | 23-31-16 | SM00014 | | | | | | | | | | | 150-199, 275 |
| 211R | 22 | PB | C | 0-0 | 23-31-16 | SM00013 | | | | | | | | | | | 150-199, 275 |
| 212B | 22 | PB | D | 4-0 | 23-31-16 | SM00010 | | | | | | | | | | | 150-199, 275 |
| 212R | 22 | PB | D | 0-0 | 23-31-16 | SM00009 | | | | | | | | | | | 150-199, 275 |
| 214B | 22 | PB | F | 3-0 | 23-31-16 | SM00014 | | | | | | | | | | | 150-199, 275 |
| 214R | 22 | PB | F | 0-0 | 23-31-16 | SM00013 | | | | | | | | | | | 150-199, 275 |
| 215B | 22 | PB | G | 4-0 | 23-31-16 | SM00016 | | | | | | | | | | | 150-199 |
| 215B | 22 | PB | G | 6-0 | 23-31-16 | SM00018 | | | | | | | | | | | 275 |
| 215R | 22 | PB | G | 0-0 | 23-31-16 | SM00015 | | | | | | | | | | | 150-199 |
| 215R | 22 | PB | G | 0-0 | 23-31-16 | SM00017 | | | | | | | | | | | 275 |
| 216B | 22 | PB | H | 4-0 | 23-31-16 | SM00014 | | | | | | | | | | | 150-199, 275 |
| 216R | 22 | PB | H | 0-0 | 23-31-16 | SM00013 | | | | | | | | | | | 150-199, 275 |
| 217B | 22 | PB | I | 6-0 | 23-31-16 | SM00016 | | | | | | | | | | | 150-199 |
| 217R | 22 | PB | I | 0-0 | 23-31-16 | SM00015 | | | | | | | | | | | 150-199 |
| 218B | 22 | PB | J | 4-0 | 23-31-16 | D03276 | | 2 | | | | | | | | | 150-199 |
| 218B | 22 | PB | J | 3-0 | 23-31-16 | D03276 | | 2 | | | | | | | | | 275 |
| 218R | 22 | PB | J | 0-0 | 23-31-16 | D03276 | | 1 | | | | | | | | | 150-199 |
| 218R | 22 | PB | J | 0-0 | 23-31-16 | D03276 | | 1 | | | | | | | | | 275 |
| 219B | 22 | PB | K | 4-0 | 23-31-16 | D05972P | | 3 | | | | | | | | | 275 |
| 219R | 22 | PB | K | 0-0 | 23-31-16 | D05972P | | 4 | | | | | | | | | 275 |
| 221B | 22 | PB | AA | 3-0 | 23-31-16 | D05970J | | 5 | | | | | | | | | 150-199 |
| 221R | 22 | PB | AA | 0-0 | 23-31-16 | D05970J | | 6 | | | | | | | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1140

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1140 | 286T1140 | | | CENTER PSU MOD (continued) | | | | | | | | | | | |
| 222B | 22 | PB | CA | 7-0 | 23-31-16 | SM00114 | | | | S | SM00110 | | | S | 150-199 |
| 222R | 22 | PB | CA | 0-0 | 23-31-16 | SM00113 | | | | S | SM00109 | | | S | 150-199 |
| 223B | 22 | PB | AB | 3-0 | 23-31-16 | D03268 | | 7 | | | SM00110 | | | S | 150-199 |
| 223R | 22 | PB | AB | 0-0 | 23-31-16 | D03268 | | 6 | | | SM00109 | | | S | 150-199 |
| 225B | 22 | PB | AD | 4-0 | 23-31-16 | SM00110 | | | | S | D03270 | | 7 | | 150-199 |
| 225R | 22 | PB | AD | 0-0 | 23-31-16 | SM00109 | | | | S | D03270 | | 6 | | 150-199 |
| 226B | 22 | PB | AG | 7-0 | 23-31-16 | SM00118 | | | | S | SM00114 | | | S | 150-199 |
| 226R | 22 | PB | AG | 0-0 | 23-31-16 | SM00117 | | | | S | SM00113 | | | S | 150-199 |
| 227B | 22 | PB | AF | 3-0 | 23-31-16 | SM00114 | | | | S | D03272 | | 7 | | 150-199 |
| 227R | 22 | PB | AF | 0-0 | 23-31-16 | SM00113 | | | | S | D03272 | | 6 | | 150-199 |
| 229B | 22 | PB | AH | 4-0 | 23-31-16 | SM00114 | | | | S | D03274 | | 7 | | 150-199 |
| 229R | 22 | PB | AH | 0-0 | 23-31-16 | SM00113 | | | | S | D03274 | | 6 | | 150-199 |
| 230B | 22 | PB | AK | 3-0 | 23-31-16 | D05972P | | 5 | | | SM00118 | | | S | 150-199 |
| 230R | 22 | PB | AK | 0-0 | 23-31-16 | D05972P | | 6 | | | SM00117 | | | S | 150-199 |
| 231B | 22 | PB | AJ | 4-0 | 23-31-16 | D03276 | | 7 | | | SM00118 | | | S | 150-199 |
| 231R | 22 | PB | AJ | 0-0 | 23-31-16 | D03276 | | 6 | | | SM00117 | | | S | 150-199 |
| 251B | 22 | PB | KA | 3-0 | 23-31-16 | D05970J | | 5 | | | SM00202 | | | S | 050-099 |
| 251R | 22 | PB | KA | 0-0 | 23-31-16 | D05970J | | 6 | | | SM00201 | | | S | 050-099 |
| 252B | 22 | PB | KB | 3-0 | 23-31-16 | D03268 | | 7 | | | SM00202 | | | S | 050-099 |
| 252R | 22 | PB | KB | 0-0 | 23-31-16 | D03268 | | 6 | | | SM00201 | | | S | 050-099 |
| 253B | 22 | PB | KC | 7-0 | 23-31-16 | SM00202 | | | | S | SM00204 | | | S | 050-099 |
| 253R | 22 | PB | KC | 0-0 | 23-31-16 | SM00201 | | | | S | SM00203 | | | S | 050-099 |
| 254B | 22 | PB | KD | 4-0 | 23-31-16 | D03270 | | 7 | | | SM00202 | | | S | 050-099 |
| 254R | 22 | PB | KD | 0-0 | 23-31-16 | D03270 | | 6 | | | SM00201 | | | S | 050-099 |
| 255B | 22 | PB | KE | 6-0 | 23-31-16 | SM00204 | | | | S | SM00206 | | | S | 050-099 |
| 255R | 22 | PB | KE | 0-0 | 23-31-16 | SM00203 | | | | S | SM00205 | | | S | 050-099 |
| 256B | 22 | PB | KF | 3-0 | 23-31-16 | D03272 | | 7 | | | SM00204 | | | S | 050-099 |
| 256R | 22 | PB | KF | 0-0 | 23-31-16 | D03272 | | 6 | | | SM00203 | | | S | 050-099 |
| 257B | 22 | PB | KG | 4-0 | 23-31-16 | D05972P | | 5 | | | SM00206 | | | S | 050-099 |
| 257R | 22 | PB | KG | 0-0 | 23-31-16 | D05972P | | 6 | | | SM00205 | | | S | 050-099 |
| 258B | 22 | PB | KH | 4-0 | 23-31-16 | D03274 | | 7 | | | SM00204 | | | S | 050-099 |
| 258R | 22 | PB | KH | 0-0 | 23-31-16 | D03274 | | 6 | | | SM00203 | | | S | 050-099 |
| 260B | 22 | PB | KJ | 3-0 | 23-31-16 | D03276 | | 7 | | | SM00206 | | | S | 050-099 |
| 260R | 22 | PB | KJ | 0-0 | 23-31-16 | D03276 | | 6 | | | SM00205 | | | S | 050-099 |
| W1141 | 286T1141 | | | ATTENDANT CALL LIGHT-RIGHT | | | | | | | | | | | |
| 001 | 22 | PA | | 6-0 | 23-42-11 | D06061P | | 1 | | | L01119 | = P | \$ | | 050-099, 150-199 |
| 002 | 22 | PA | | 6-0 | 23-34-13 | D06061P | | 2 | | | L01134 | = P | \$ | | 050-099, 150-199 |
| 003 | 22 | PA | | 6-0 | 33-25-11 | D06061P | | 3 | | | L01160 | = P | \$ | | 050-099, 150-199 |

WIRE LIST
D280T132

91-21-11
Section W1140
Page 4
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1141 | 286T1141 | | | ATTENDANT CALL LIGHT-RIGHT (continued) | | | | | | | | | | | | | |
| 004 | 20 | | PA | 6-0 | 23-42-11 | D06061P | | 4 | | | | | L01119 | =G | \$ | | 050-099, 150-199 |
| W1142 | 286T1142 | | | CENTER PSU MOD | | | | | | | | | | | | | |
| 001 | 18 | | PA | 3-0 | 33-24-13 | D05972J | | 1 | DL | | | | SM00064 | | | S | 275 |
| 001 | 18 | | PA | 3-0 | 33-24-13 | D05972J | | 1 | DL | | | | SM00001 | | | S | 276-299 |
| 002 | 18 | | PA | 2-0 | 33-24-13 | D05972J | | 2 | DL | | | | SM00065 | | | S | 275 |
| 002 | 18 | | PA | 3-0 | 33-24-13 | D05972J | | 2 | DL | | | | SM00002 | | | S | 276-299 |
| 003 | 20 | | PA | 3-0 | 33-24-13 | D03278 | | 4 | | | | | SM00064 | | | S | 275 |
| 003 | 18 | | PA | 7-0 | 33-24-13 | SM00001 | | | S | | | | SM00003 | | | S | 276-299 |
| 004 | 20 | | PA | 2-0 | 33-24-13 | D03278 | | 3 | | | | | SM00065 | | | S | 275 |
| 004 | 18 | | PA | 7-0 | 33-24-13 | SM00002 | | | S | | | | SM00004 | | | S | 276-299 |
| 005 | 20 | | PA | 8-0 | 33-24-13 | D03278 | | 5 | | | | | GD05080 | A.. | | S | 275 |
| 005 | 18 | | PA | 6-0 | 33-24-13 | SM00003 | | | S | | | | SM00005 | | | S | 276-299 |
| 006 | 18 | | PA | 6-0 | 33-24-13 | SM00001 | | | S | | | | SM00064 | | | S | 275 |
| 006 | 18 | | PA | 6-0 | 33-24-13 | SM00004 | | | S | | | | SM00006 | | | S | 276-299 |
| 007 | 18 | | PA | 7-0 | 33-24-13 | SM00002 | | | S | | | | SM00065 | | | S | 275 |
| 007 | 18 | | PA | 4-0 | 33-24-13 | SM00005 | | | S | | | | D05974P | | 1 | DK | 276-299 |
| 008 | 20 | | PA | 3-0 | 33-24-13 | SM00064 | | | S | | | | D03280 | | 4 | | 275 |
| 008 | 18 | | PA | 4-0 | 33-24-13 | SM00006 | | | S | | | | D05974P | | 2 | DK | 276-299 |
| 009 | 20 | | PA | 3-0 | 33-24-13 | SM00065 | | | S | | | | D03280 | | 3 | | 275 |
| 010 | 20 | | PA | 6-0 | 33-24-13 | GD05080 | | A.. | 2 | | | | D03280 | | 5 | | 275 |
| 013 | 20 | | PA | 2-0 | 33-24-13 | D03282 | | 4 | | | | | SM00001 | | | S | 275 |
| 014 | 20 | | PA | 2-0 | 33-24-13 | D03282 | | 3 | | | | | SM00002 | | | S | 275 |
| 015 | 20 | | PA | 5-0 | 33-24-13 | D03282 | | 5 | | | | | GD05080 | A.. | 2 | | 275 |
| 018 | 20 | | PA | 3-0 | 33-24-13 | D02052 | | 4 | | | | | SM00001 | | | S | 275 |
| 019 | 20 | | PA | 3-0 | 33-24-13 | D02052 | | 3 | | | | | SM00002 | | | S | 275 |
| 020 | 20 | | PA | 4-0 | 33-24-13 | D02052 | | 5 | | | | | GD04874 | A.. | 2 | | 275 |
| 021 | 18 | | PA | 7-0 | 33-24-13 | SM00001 | | | S | | | | SM00003 | | | S | 275 |
| 022 | 18 | | PA | 7-0 | 33-24-13 | SM00002 | | | S | | | | SM00004 | | | S | 275 |
| 023 | 20 | | PA | 2-0 | 33-24-13 | D02054 | | 4 | | | | | SM00003 | | | S | 275 |
| 024 | 20 | | PA | 3-0 | 33-24-13 | D02054 | | 3 | | | | | SM00004 | | | S | 275 |
| 025 | 20 | | PA | 6-0 | 33-24-13 | D02054 | | 5 | | | | | GD04876 | A.. | 2 | | 275 |
| 026 | 18 | | PA | 3-0 | 33-24-13 | D05974P | | 1 | DK | | | | SM00004 | | | S | 275 |
| 027 | 18 | | PA | 4-0 | 33-24-13 | D05974P | | 2 | DK | | | | SM00003 | | | S | 275 |
| 103 | 20 | | PA | 3-0 | 33-24-13 | D03278 | | 3 | | | | | SM00002 | | | S | 276-299 |
| 104 | 20 | | PA | 3-0 | 33-24-13 | D03278 | | 4 | | | | | SM00001 | | | S | 276-299 |
| 105 | 20 | | PA | 8-0 | 33-24-13 | D03278 | | 5 | | | | | GD05080 | A.. | 2 | | 276-299 |
| 113 | 20 | | PA | 4-0 | 33-24-13 | D03280 | | 3 | | | | | SM00002 | | | S | 276-299 |
| 114 | 20 | | PA | 4-0 | 33-24-13 | D03280 | | 4 | | | | | SM00001 | | | S | 276-299 |

WIRE LIST

D280T132

91-21-11

Section W1140

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1142 | 286T1142 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | | |
| 115 | 20 | | PA | | 6-0 | 33-24-13 | D03280 | | 5 | | | | GD05080 | A.. | 2 | | 276-299 |
| 123 | 20 | | PA | | 3-0 | 33-24-13 | D03282 | | 3 | | | | SM00004 | | S | | 276-299 |
| 124 | 20 | | PA | | 3-0 | 33-24-13 | D03282 | | 4 | | | | SM00003 | | S | | 276-299 |
| 125 | 20 | | PA | | 5-0 | 33-24-13 | D03282 | | 5 | | | | GD05080 | A.. | 2 | | 276-299 |
| 133 | 20 | | PA | | 4-0 | 33-24-13 | D02052 | | 3 | | | | SM00004 | | S | | 276-299 |
| 134 | 20 | | PA | | 4-0 | 33-24-13 | D02052 | | 4 | | | | SM00003 | | S | | 276-299 |
| 135 | 20 | | PA | | 5-0 | 33-24-13 | D02052 | | 5 | | | | GD04874 | A.. | 2 | | 276-299 |
| 143 | 20 | | PA | | 3-0 | 33-24-13 | D02054 | | 3 | | | | SM00006 | | S | | 276-299 |
| 144 | 20 | | PA | | 3-0 | 33-24-13 | D02054 | | 4 | | | | SM00005 | | S | | 276-299 |
| 145 | 20 | | PA | | 6-0 | 33-24-13 | D02054 | | 5 | | | | GD04876 | A.. | 2 | | 276-299 |
| 201B | 22 | | PB | A | 3-0 | 23-31-16 | D05972J | | 3 | | | | SM00020 | | S | | 275 |
| 201B | 22 | | PB | IA | 3-0 | 23-31-16 | D05972J | | 3 | | | | SM00102 | | S | | 276-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-16 | D05972J | | 4 | | | | SM00019 | | S | | 275 |
| 201R | 22 | | PB | IA | 0-0 | 23-31-16 | D05972J | | 4 | | | | SM00101 | | S | | 276-299 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-16 | D03278 | | 2 | | | | SM00102 | | S | | 276-299 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-16 | D03278 | | 1 | | | | SM00101 | | S | | 276-299 |
| 203B | 22 | | PB | IC | 7-0 | 23-31-16 | SM00102 | | | S | | | SM00104 | | S | | 276-299 |
| 203R | 22 | | PB | IC | 0-0 | 23-31-16 | SM00101 | | | S | | | SM00103 | | S | | 276-299 |
| 204B | 22 | | PB | ID | 4-0 | 23-31-16 | D03280 | | 2 | | | | SM00102 | | S | | 276-299 |
| 204R | 22 | | PB | ID | 0-0 | 23-31-16 | D03280 | | 1 | | | | SM00101 | | S | | 276-299 |
| 205B | 22 | | PB | IE | 6-0 | 23-31-16 | SM00104 | | | S | | | SM00106 | | S | | 276-299 |
| 205R | 22 | | PB | IE | 0-0 | 23-31-16 | SM00103 | | | S | | | SM00105 | | S | | 276-299 |
| 206B | 22 | | PB | IF | 3-0 | 23-31-16 | D03282 | | 2 | | | | SM00104 | | S | | 276-299 |
| 206R | 22 | | PB | IF | 0-0 | 23-31-16 | D03282 | | 1 | | | | SM00103 | | S | | 276-299 |
| 207B | 22 | | PB | IG | 4-0 | 23-31-16 | SM00106 | | | S | | | D05974P | | 3 | | 276-299 |
| 207R | 22 | | PB | IG | 0-0 | 23-31-16 | SM00105 | | | S | | | D05974P | | 4 | | 276-299 |
| 208B | 22 | | PB | IH | 4-0 | 23-31-16 | D02052 | | 2 | | | | SM00104 | | S | | 276-299 |
| 208R | 22 | | PB | IH | 0-0 | 23-31-16 | D02052 | | 1 | | | | SM00103 | | S | | 276-299 |
| 210B | 22 | | PB | IJ | 3-0 | 23-31-16 | D02054 | | 2 | | | | SM00106 | | S | | 276-299 |
| 210R | 22 | | PB | IJ | 0-0 | 23-31-16 | D02054 | | 1 | | | | SM00105 | | S | | 276-299 |
| 220B | 22 | | PB | B | 3-0 | 23-31-16 | D03278 | | 2 | | | | SM00020 | | S | | 275 |
| 220R | 22 | | PB | B | 0-0 | 23-31-16 | D03278 | | 1 | | | | SM00019 | | S | | 275 |
| 221B | 22 | | PB | C | 7-0 | 23-31-16 | SM00026 | | | S | | | SM00020 | | S | | 275 |
| 221R | 22 | | PB | C | 0-0 | 23-31-16 | SM00025 | | | S | | | SM00019 | | S | | 275 |
| 222B | 22 | | PB | D | 3-0 | 23-31-16 | D03280 | | 2 | | | | SM00020 | | S | | 275 |
| 222R | 22 | | PB | D | 0-0 | 23-31-16 | D03280 | | 1 | | | | SM00019 | | S | | 275 |
| 224B | 22 | | PB | F | 3-0 | 23-31-16 | D03282 | | 2 | | | | SM00026 | | S | | 275 |
| 224R | 22 | | PB | F | 0-0 | 23-31-16 | D03282 | | 1 | | | | SM00025 | | S | | 275 |
| 226B | 22 | | PB | H | 6-0 | 23-31-16 | SM00026 | | | S | | | SM00028 | | S | | 275 |

WIRE LIST

D280T132

91-21-11
 Section W1140
 Page 6
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-----------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1142 | 286T1142 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | |
| 226R | 22 | PB | H | 0-0 | 23-31-16 | SM00025 | | S | | SM00027 | | S | | 275 | | |
| 227B | 22 | PB | I | 4-0 | 23-31-16 | D02052 | 2 | | | SM00026 | | S | | 275 | | |
| 227R | 22 | PB | I | 0-0 | 23-31-16 | D02052 | 1 | | | SM00025 | | S | | 275 | | |
| 228B | 22 | PB | J | 4-0 | 23-31-16 | SM00028 | | S | | D05974P | 3 | | | 275 | | |
| 228R | 22 | PB | J | 0-0 | 23-31-16 | SM00027 | | S | | D05974P | 4 | | | 275 | | |
| 229B | 22 | PB | K | 3-0 | 23-31-16 | SM00028 | | S | | D02054 | 2 | | | 275 | | |
| 229R | 22 | PB | K | 0-0 | 23-31-16 | SM00027 | | S | | D02054 | 1 | | | 275 | | |
| W1144 | 286T1144 | | | CENTER PSU MOD | | | | | | | | | | | | |
| 001 | 18 | PA | | 3-0 | 33-24-13 | D05976J | 1 | DL | | SM00001 | | S | | 050-099 | | |
| 002 | 18 | PA | | 3-0 | 33-24-13 | D05976J | 2 | DL | | SM00002 | | S | | 050-099 | | |
| 003 | 18 | PA | | 7-0 | 33-24-13 | SM00001 | | S | | SM00003 | | S | | 050-099 | | |
| 004 | 18 | PA | | 7-0 | 33-24-13 | SM00002 | | S | | SM00004 | | S | | 050-099 | | |
| 005 | 18 | PA | | 6-0 | 33-24-13 | SM00003 | | S | | SM00005 | | S | | 050-099 | | |
| 006 | 18 | PA | | 6-0 | 33-24-13 | SM00004 | | S | | SM00006 | | S | | 050-099 | | |
| 007 | 18 | PA | | 4-0 | 33-24-13 | SM00005 | | S | | D05978P | 1 | DK | | 050-099 | | |
| 008 | 18 | PA | | 4-0 | 33-24-13 | SM00006 | | S | | D05978P | 2 | DK | | 050-099 | | |
| 103 | 22 | PA | | 3-0 | 33-24-13 | SM00002 | | S | | D03286 | 3 | | | 050-099 | | |
| 104 | 22 | PA | | 3-0 | 33-24-13 | SM00001 | | S | | D03286 | 4 | | | 050-099 | | |
| 105 | 20 | PA | | 8-0 | 33-24-13 | D03286 | 5 | | | GD01950 | A.. | 2 | | 050-099 | | |
| 113 | 22 | PA | | 4-0 | 33-24-13 | SM00002 | | S | | D03288 | 3 | | | 050-099 | | |
| 114 | 22 | PA | | 4-0 | 33-24-13 | SM00001 | | S | | D03288 | 4 | | | 050-099 | | |
| 115 | 20 | PA | | 6-0 | 33-24-13 | D03288 | 5 | | | GD01950 | A.. | 2 | | 050-099 | | |
| 123 | 22 | PA | | 3-0 | 33-24-13 | SM00004 | | S | | D03290 | 3 | | | 050-099 | | |
| 124 | 22 | PA | | 3-0 | 33-24-13 | SM00003 | | S | | D03290 | 4 | | | 050-099 | | |
| 125 | 20 | PA | | 5-0 | 33-24-13 | D03290 | 5 | | | GD01950 | A.. | 2 | | 050-099 | | |
| 133 | 22 | PA | | 4-0 | 33-24-13 | SM00004 | | S | | D03292 | 3 | | | 050-099 | | |
| 134 | 22 | PA | | 4-0 | 33-24-13 | SM00003 | | S | | D03292 | 4 | | | 050-099 | | |
| 135 | 20 | PA | | 5-0 | 33-24-13 | D03292 | 5 | | | GD01952 | A.. | 2 | | 050-099 | | |
| 143 | 22 | PA | | 3-0 | 33-24-13 | SM00006 | | S | | D03294 | 3 | | | 050-099 | | |
| 144 | 22 | PA | | 3-0 | 33-24-13 | SM00005 | | S | | D03294 | 4 | | | 050-099 | | |
| 145 | 20 | PA | | 6-0 | 33-24-13 | D03294 | 5 | | | GD01952 | A.. | 2 | | 050-099 | | |
| 201B | 22 | PB | IA | 3-0 | 23-31-16 | D05976J | 3 | | | SM00102 | | S | | 050-099 | | |
| 201R | 22 | PB | IA | 0-0 | 23-31-16 | D05976J | 4 | | | SM00101 | | S | | 050-099 | | |
| 202B | 22 | PB | IB | 3-0 | 23-31-16 | SM00102 | | S | | D03286 | 2 | | | 050-099 | | |
| 202R | 22 | PB | IB | 0-0 | 23-31-16 | SM00101 | | S | | D03286 | 1 | | | 050-099 | | |
| 203B | 22 | PB | IC | 7-0 | 23-31-16 | SM00102 | | S | | SM00104 | | S | | 050-099 | | |
| 203R | 22 | PB | IC | 0-0 | 23-31-16 | SM00101 | | S | | SM00103 | | S | | 050-099 | | |
| 204B | 22 | PB | ID | 4-0 | 23-31-16 | SM00102 | | S | | D03288 | 2 | | | 050-099 | | |

WIRE LIST

D280T132

91-21-11

Section W1140

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1144 | 286T1144 | | | CENTER PSU MOD (continued) | | | | | | | | | | | |
| 204R | 22 | PB | ID | 0-0 | 23-31-16 | SM00101 | | | S | | D03288 | 1 | | | 050-099 |
| 205B | 22 | PB | IE | 6-0 | 23-31-16 | SM00104 | | | S | | SM00106 | | S | | 050-099 |
| 205R | 22 | PB | IE | 0-0 | 23-31-16 | SM00103 | | | S | | SM00105 | | S | | 050-099 |
| 206B | 22 | PB | IF | 3-0 | 23-31-16 | SM00104 | | | S | | D03290 | 2 | | | 050-099 |
| 206R | 22 | PB | IF | 0-0 | 23-31-16 | SM00103 | | | S | | D03290 | 1 | | | 050-099 |
| 207B | 22 | PB | IG | 4-0 | 23-31-16 | SM00106 | | | S | | D05978P | 3 | | | 050-099 |
| 207R | 22 | PB | IG | 0-0 | 23-31-16 | SM00105 | | | S | | D05978P | 4 | | | 050-099 |
| 208B | 22 | PB | IH | 4-0 | 23-31-16 | SM00104 | | | S | | D03292 | 2 | | | 050-099 |
| 208R | 22 | PB | IH | 0-0 | 23-31-16 | SM00103 | | | S | | D03292 | 1 | | | 050-099 |
| 210B | 22 | PB | IJ | 3-0 | 23-31-16 | SM00106 | | | S | | D03294 | 2 | | | 050-099 |
| 210R | 22 | PB | IJ | 0-0 | 23-31-16 | SM00105 | | | S | | D03294 | 1 | | | 050-099 |
| 251B | 22 | PB | KA | 3-0 | 23-31-16 | D05976J | | 5 | | | SM00202 | | S | | 050-099 |
| 251R | 22 | PB | KA | 0-0 | 23-31-16 | D05976J | | 6 | | | SM00201 | | S | | 050-099 |
| 252B | 22 | PB | KB | 3-0 | 23-31-16 | D03286 | | 7 | | | SM00202 | | S | | 050-099 |
| 252R | 22 | PB | KB | 0-0 | 23-31-16 | D03286 | | 6 | | | SM00201 | | S | | 050-099 |
| 253B | 22 | PB | KC | 7-0 | 23-31-16 | SM00202 | | | S | | SM00204 | | S | | 050-099 |
| 253R | 22 | PB | KC | 0-0 | 23-31-16 | SM00201 | | | S | | SM00203 | | S | | 050-099 |
| 254B | 22 | PB | KD | 4-0 | 23-31-16 | D03288 | | 7 | | | SM00202 | | S | | 050-099 |
| 254R | 22 | PB | KD | 0-0 | 23-31-16 | D03288 | | 6 | | | SM00201 | | S | | 050-099 |
| 255B | 22 | PB | KE | 6-0 | 23-31-16 | SM00204 | | | S | | SM00206 | | S | | 050-099 |
| 255R | 22 | PB | KE | 0-0 | 23-31-16 | SM00203 | | | S | | SM00205 | | S | | 050-099 |
| 256B | 22 | PB | KF | 3-0 | 23-31-16 | D03290 | | 7 | | | SM00204 | | S | | 050-099 |
| 256R | 22 | PB | KF | 0-0 | 23-31-16 | D03290 | | 6 | | | SM00203 | | S | | 050-099 |
| 257B | 22 | PB | KG | 4-0 | 23-31-16 | D05978P | | 5 | | | SM00206 | | S | | 050-099 |
| 257R | 22 | PB | KG | 0-0 | 23-31-16 | D05978P | | 6 | | | SM00205 | | S | | 050-099 |
| 258B | 22 | PB | KH | 4-0 | 23-31-16 | D03292 | | 7 | | | SM00204 | | S | | 050-099 |
| 258R | 22 | PB | KH | 0-0 | 23-31-16 | D03292 | | 6 | | | SM00203 | | S | | 050-099 |
| 260B | 22 | PB | KJ | 3-0 | 23-31-16 | D03294 | | 7 | | | SM00206 | | S | | 050-099 |
| 260R | 22 | PB | KJ | 0-0 | 23-31-16 | D03294 | | 6 | | | SM00205 | | S | | 050-099 |
| W1146 | 286T1146 | | | CENTER PSU MOD | | | | | | | | | | | |
| 001 | 18 | PA | | 3-0 | 33-24-13 | D05978J | | 1 | DL | | SM00001 | | S | | 050-099, 276-299 |
| 001 | 18 | PA | | 3-0 | 33-24-13 | D05978J | | 1 | DL | | SM00064 | | S | | 150-199, 275 |
| 002 | 18 | PA | | 3-0 | 33-24-13 | D05978J | | 2 | DL | | SM00002 | | S | | 050-099, 276-299 |
| 002 | 18 | PA | | 3-0 | 33-24-13 | D05978J | | 2 | DL | | SM00063 | | S | | 150-199, 275 |
| 003 | 18 | PA | | 7-0 | 33-24-13 | SM00001 | | | S | | SM00003 | | S | | 050-099, 276-299 |
| 003 | 20 | PA | | 3-0 | 33-24-13 | D03296 | | 3 | | | SM00063 | | S | | 150-199, 275 |
| 004 | 18 | PA | | 7-0 | 33-24-13 | SM00002 | | | S | | SM00004 | | S | | 050-099, 276-299 |
| 004 | 20 | PA | | 3-0 | 33-24-13 | D03296 | | 4 | | | SM00064 | | S | | 150-199, 275 |

WIRE LIST
D280T132

91-21-11
Section W1140
Page 8
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-----------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1146 | 286T1146 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | |
| 005 | 18 | PA | | 6-0 | 33-24-13 | SM00003 | | S | | SM00005 | | S | | 050-099, 276-299 | | |
| 005 | 20 | PA | | 8-0 | 33-24-13 | D03296 | 5 | | | GD01906 | A.. | 2 | | 150-199 | | |
| 005 | 20 | PA | | 4-0 | 33-24-13 | D03296 | 5 | | | GD01748 | A.. | 2 | | 275 | | |
| 006 | 18 | PA | | 6-0 | 33-24-13 | SM00004 | | S | | SM00006 | | S | | 050-099, 276-299 | | |
| 006 | 18 | PA | | 6-0 | 33-24-13 | SM00068 | | S | | SM00064 | | S | | 150-199 | | |
| 006 | 18 | PA | | 7-0 | 33-24-13 | SM00068 | | S | | SM00064 | | S | | 275 | | |
| 007 | 18 | PA | | 4-0 | 33-24-13 | SM00005 | | S | | D05980P | 1 | DK | | 050-099, 276-299 | | |
| 007 | 18 | PA | | 6-0 | 33-24-13 | SM00067 | | S | | SM00063 | | S | | 150-199 | | |
| 007 | 18 | PA | | 7-0 | 33-24-13 | SM00067 | | S | | SM00063 | | S | | 275 | | |
| 008 | 18 | PA | | 4-0 | 33-24-13 | SM00006 | | S | | D05980P | 2 | DK | | 050-099, 276-299 | | |
| 008 | 20 | PA | | 4-0 | 33-24-13 | SM00063 | | S | | D03298 | 3 | | | 150-199, 275 | | |
| 009 | 20 | PA | | 4-0 | 33-24-13 | SM00064 | | S | | D03298 | 4 | | | 150-199, 275 | | |
| 010 | 20 | PA | | 6-0 | 33-24-13 | GD01906 | A.. | 2 | | D03298 | 5 | | | 150-199 | | |
| 010 | 20 | PA | | 10-0 | 33-24-13 | GD01750 | A.. | 2 | | D03298 | 5 | | | 275 | | |
| 013 | 20 | PA | | 3-0 | 33-24-13 | D03300 | 3 | | | SM00067 | | S | | 150-199, 275 | | |
| 014 | 20 | PA | | 3-0 | 33-24-13 | D03300 | 4 | | | SM00068 | | S | | 150-199, 275 | | |
| 015 | 20 | PA | | 7-0 | 33-24-13 | D03300 | 5 | | | GD01750 | A.. | 2 | | 150-199, 275 | | |
| 016 | 18 | PA | | 7-0 | 33-24-13 | SM00068 | | S | | SM00035 | | S | | 150-199, 275 | | |
| 017 | 18 | PA | | 7-0 | 33-24-13 | SM00067 | | S | | SM00036 | | S | | 150-199, 275 | | |
| 018 | 20 | PA | | 4-0 | 33-24-13 | D03302 | 4 | | | SM00068 | | S | | 150-199, 275 | | |
| 019 | 20 | PA | | 4-0 | 33-24-13 | D03302 | 3 | | | SM00067 | | S | | 150-199, 275 | | |
| 020 | 20 | PA | | 4-0 | 33-24-13 | D03302 | 5 | | | GD01750 | A.. | 2 | | 150-199 | | |
| 020 | 20 | PA | | 5-0 | 33-24-13 | D03302 | 5 | | | GD01750 | A.. | 2 | | 275 | | |
| 023 | 20 | PA | | 4-0 | 33-24-13 | D03378 | 4 | | | SM00035 | | S | | 150-199 | | |
| 023 | 20 | PA | | 3-0 | 33-24-13 | D03378 | 4 | | | SM00035 | | S | | 275 | | |
| 024 | 20 | PA | | 4-0 | 33-24-13 | D03378 | 3 | | | SM00036 | | S | | 150-199 | | |
| 024 | 20 | PA | | 3-0 | 33-24-13 | D03378 | 3 | | | SM00036 | | S | | 275 | | |
| 025 | 20 | PA | | 6-0 | 33-24-13 | D03378 | 5 | | | GD01750 | A.. | 2 | | 150-199, 275 | | |
| 026 | 18 | PA | | 3-0 | 33-24-13 | D05980P | 1 | DK | | SM00035 | | S | | 150-199 | | |
| 026 | 18 | PA | | 4-0 | 33-24-13 | D05980P | 1 | DK | | SM00035 | | S | | 275 | | |
| 027 | 18 | PA | | 3-0 | 33-24-13 | D05980P | 2 | DK | | SM00036 | | S | | 150-199 | | |
| 027 | 18 | PA | | 4-0 | 33-24-13 | D05980P | 2 | DK | | SM00036 | | S | | 275 | | |
| 103 | 22 | PA | | 3-0 | 33-24-13 | SM00002 | | S | | D03296 | 3 | | | 050-099 | | |
| 103 | 20 | PA | | 3-0 | 33-24-13 | D03296 | 3 | | | SM00002 | | S | | 276-299 | | |
| 104 | 22 | PA | | 3-0 | 33-24-13 | SM00001 | | S | | D03296 | 4 | | | 050-099 | | |
| 104 | 20 | PA | | 3-0 | 33-24-13 | D03296 | 4 | | | SM00001 | | S | | 276-299 | | |
| 105 | 20 | PA | | 4-0 | 33-24-13 | D03296 | 5 | | | GD01748 | A.. | 2 | | 050-099, 276-299 | | |
| 113 | 22 | PA | | 4-0 | 33-24-13 | SM00002 | | S | | D03298 | 3 | | | 050-099 | | |
| 113 | 20 | PA | | 4-0 | 33-24-13 | D03298 | 3 | | | SM00002 | | S | | 276-299 | | |

WIRE LIST

D280T132

91-21-11

Section W1140

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1146 | 286T1146 | | | CENTER PSU MOD (continued) | | | | | | | | | | | |
| 114 | 22 | | PA | | 4-0 | 33-24-13 | SM00001 | | S | | D03298 | | 4 | | 050-099 |
| 114 | 20 | | PA | | 4-0 | 33-24-13 | D03298 | 4 | | | SM00001 | | S | | 276-299 |
| 115 | 20 | | PA | | 6-0 | 33-24-13 | D03298 | 5 | | | GD01906 | A.. | 2 | | 050-099, 276-299 |
| 123 | 22 | | PA | | 3-0 | 33-24-13 | SM00004 | | S | | D03300 | | 3 | | 050-099 |
| 123 | 20 | | PA | | 3-0 | 33-24-13 | D03300 | 3 | | | SM00004 | | S | | 276-299 |
| 124 | 22 | | PA | | 3-0 | 33-24-13 | SM00003 | | S | | D03300 | | 4 | | 050-099 |
| 124 | 20 | | PA | | 3-0 | 33-24-13 | D03300 | 4 | | | SM00003 | | S | | 276-299 |
| 125 | 20 | | PA | | 5-0 | 33-24-13 | D03300 | 5 | | | GD01906 | A.. | 2 | | 050-099, 276-299 |
| 133 | 22 | | PA | | 4-0 | 33-24-13 | SM00004 | | S | | D03302 | | 3 | | 050-099 |
| 133 | 20 | | PA | | 4-0 | 33-24-13 | D03302 | 3 | | | SM00004 | | S | | 276-299 |
| 134 | 22 | | PA | | 4-0 | 33-24-13 | SM00003 | | S | | D03302 | | 4 | | 050-099 |
| 134 | 20 | | PA | | 4-0 | 33-24-13 | D03302 | 4 | | | SM00003 | | S | | 276-299 |
| 135 | 20 | | PA | | 5-0 | 33-24-13 | D03302 | 5 | | | GD01750 | A.. | 2 | | 050-099, 276-299 |
| 143 | 22 | | PA | | 3-0 | 33-24-13 | SM00006 | | S | | D03378 | | 3 | | 050-099 |
| 143 | 20 | | PA | | 3-0 | 33-24-13 | D03378 | 3 | | | SM00006 | | S | | 276-299 |
| 144 | 22 | | PA | | 3-0 | 33-24-13 | SM00005 | | S | | D03378 | | 4 | | 050-099 |
| 144 | 20 | | PA | | 3-0 | 33-24-13 | D03378 | 4 | | | SM00005 | | S | | 276-299 |
| 145 | 20 | | PA | | 6-0 | 33-24-13 | D03378 | 5 | | | GD01750 | A.. | 2 | | 050-099, 276-299 |
| 201B | 22 | | PB | IA | 3-0 | 23-31-16 | D05978J | 3 | | | SM00102 | | S | | 050-099, 276-299 |
| 201B | 22 | | PB | A | 3-0 | 23-31-16 | D05978J | 3 | | | SM00070 | | S | | 150-199, 275 |
| 201R | 22 | | PB | IA | 0-0 | 23-31-16 | D05978J | 4 | | | SM00101 | | S | | 050-099, 276-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-16 | D05978J | 4 | | | SM00071 | | S | | 150-199, 275 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-16 | SM00102 | | S | | D03296 | | 2 | | 050-099 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-16 | D03296 | 2 | | | SM00102 | | S | | 276-299 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-16 | SM00101 | | S | | D03296 | | 1 | | 050-099 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-16 | D03296 | 1 | | | SM00101 | | S | | 276-299 |
| 203B | 22 | | PB | IC | 7-0 | 23-31-16 | SM00102 | | S | | SM00104 | | S | | 050-099, 276-299 |
| 203B | 22 | | PB | C | 4-0 | 23-31-16 | D03378 | 2 | | | SM00002 | | S | | 150-199 |
| 203B | 22 | | PB | C | 3-0 | 23-31-16 | D03378 | 2 | | | SM00002 | | S | | 275 |
| 203R | 22 | | PB | IC | 0-0 | 23-31-16 | SM00101 | | S | | SM00103 | | S | | 050-099, 276-299 |
| 203R | 22 | | PB | C | 0-0 | 23-31-16 | D03378 | 1 | | | SM00001 | | S | | 150-199, 275 |
| 204B | 22 | | PB | ID | 4-0 | 23-31-16 | SM00102 | | S | | D03298 | | 2 | | 050-099 |
| 204B | 22 | | PB | D | 3-0 | 23-31-16 | D05980P | 3 | | | SM00002 | | S | | 150-199 |
| 204B | 22 | | PB | D | 4-0 | 23-31-16 | D05980P | 3 | | | SM00002 | | S | | 275 |
| 204B | 22 | | PB | ID | 4-0 | 23-31-16 | D03298 | 2 | | | SM00102 | | S | | 276-299 |
| 204R | 22 | | PB | ID | 0-0 | 23-31-16 | SM00101 | | S | | D03298 | | 1 | | 050-099 |
| 204R | 22 | | PB | D | 0-0 | 23-31-16 | D05980P | 4 | | | SM00001 | | S | | 150-199, 275 |
| 204R | 22 | | PB | ID | 0-0 | 23-31-16 | D03298 | 1 | | | SM00101 | | S | | 276-299 |
| 205B | 22 | | PB | IE | 6-0 | 23-31-16 | SM00104 | | S | | SM00106 | | S | | 050-099, 276-299 |

WIRE LIST

D280T132

91-21-11

Section W1140

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1146 | 286T1146 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | | |
| 205R | 22 | PB | IE | 0-0 | 23-31-16 | SM00103 | | | | S | | | | SM00105 | | S | 050-099, 276-299 |
| 206B | 22 | PB | IF | 3-0 | 23-31-16 | SM00104 | | | | S | | | | D03300 | 2 | | 050-099 |
| 206B | 22 | PB | IF | 3-0 | 23-31-16 | D03300 | | 2 | | | | | | SM00104 | | S | 276-299 |
| 206R | 22 | PB | IF | 0-0 | 23-31-16 | SM00103 | | | | S | | | | D03300 | 1 | | 050-099 |
| 206R | 22 | PB | IF | 0-0 | 23-31-16 | D03300 | | 1 | | | | | | SM00103 | | S | 276-299 |
| 207B | 22 | PB | IG | 4-0 | 23-31-16 | SM00106 | | | | S | | | | D05980P | 3 | | 050-099, 276-299 |
| 207R | 22 | PB | IG | 0-0 | 23-31-16 | SM00105 | | | | S | | | | D05980P | 4 | | 050-099, 276-299 |
| 208B | 22 | PB | IH | 4-0 | 23-31-16 | SM00104 | | | | S | | | | D03302 | 2 | | 050-099 |
| 208B | 22 | PB | IH | 4-0 | 23-31-16 | D03302 | | 2 | | | | | | SM00104 | | S | 276-299 |
| 208R | 22 | PB | IH | 0-0 | 23-31-16 | SM00103 | | | | S | | | | D03302 | 1 | | 050-099 |
| 208R | 22 | PB | IH | 0-0 | 23-31-16 | D03302 | | 1 | | | | | | SM00103 | | S | 276-299 |
| 209B | 22 | PB | AA | 3-0 | 23-31-16 | D05978J | | 5 | | | | | | SM00170 | | S | 150-199 |
| 209R | 22 | PB | AA | 0-0 | 23-31-16 | D05978J | | 6 | | | | | | SM00171 | | S | 150-199 |
| 210B | 22 | PB | IJ | 3-0 | 23-31-16 | SM00106 | | | | S | | | | D03378 | 2 | | 050-099 |
| 210B | 22 | PB | AF | 6-0 | 23-31-16 | SM00174 | | | | S | | | | SM00170 | | S | 150-199 |
| 210B | 22 | PB | IJ | 3-0 | 23-31-16 | D03378 | | 2 | | | | | | SM00106 | | S | 276-299 |
| 210R | 22 | PB | IJ | 0-0 | 23-31-16 | SM00105 | | | | S | | | | D03378 | 1 | | 050-099 |
| 210R | 22 | PB | AF | 0-0 | 23-31-16 | SM00175 | | | | S | | | | SM00171 | | S | 150-199 |
| 210R | 22 | PB | IJ | 0-0 | 23-31-16 | D03378 | | 1 | | | | | | SM00105 | | S | 276-299 |
| 211B | 22 | PB | AH | 4-0 | 23-31-16 | D03298 | | 7 | | | | | | SM00170 | | S | 150-199 |
| 211R | 22 | PB | AH | 0-0 | 23-31-16 | D03298 | | 6 | | | | | | SM00171 | | S | 150-199 |
| 212B | 22 | PB | AE | 3-0 | 23-31-16 | D03296 | | 7 | | | | | | SM00170 | | S | 150-199 |
| 212R | 22 | PB | AE | 0-0 | 23-31-16 | D03296 | | 6 | | | | | | SM00171 | | S | 150-199 |
| 230B | 22 | PB | E | 3-0 | 23-31-16 | D03296 | | 2 | | | | | | SM00070 | | S | 150-199, 275 |
| 230R | 22 | PB | E | 0-0 | 23-31-16 | D03296 | | 1 | | | | | | SM00071 | | S | 150-199, 275 |
| 231B | 22 | PB | F | 6-0 | 23-31-16 | SM00074 | | | | S | | | | SM00070 | | S | 150-199 |
| 231B | 22 | PB | F | 7-0 | 23-31-16 | SM00074 | | | | S | | | | SM00070 | | S | 275 |
| 231R | 22 | PB | F | 0-0 | 23-31-16 | SM00075 | | | | S | | | | SM00071 | | S | 150-199, 275 |
| 234B | 22 | PB | H | 4-0 | 23-31-16 | D03298 | | 2 | | | | | | SM00070 | | S | 150-199, 275 |
| 234R | 22 | PB | H | 0-0 | 23-31-16 | D03298 | | 1 | | | | | | SM00071 | | S | 150-199, 275 |
| 235B | 22 | PB | I | 3-0 | 23-31-16 | D03300 | | 2 | | | | | | SM00074 | | S | 150-199, 275 |
| 235R | 22 | PB | I | 0-0 | 23-31-16 | D03300 | | 1 | | | | | | SM00075 | | S | 150-199, 275 |
| 236B | 22 | PB | J | 4-0 | 23-31-16 | D03302 | | 2 | | | | | | SM00074 | | S | 150-199, 275 |
| 236R | 22 | PB | J | 0-0 | 23-31-16 | D03302 | | 1 | | | | | | SM00075 | | S | 150-199, 275 |
| 237B | 22 | PB | K | 7-0 | 23-31-16 | SM00074 | | | | S | | | | SM00002 | | S | 150-199, 275 |
| 237R | 22 | PB | K | 0-0 | 23-31-16 | SM00075 | | | | S | | | | SM00001 | | S | 150-199, 275 |
| 251B | 22 | PB | KA | 3-0 | 23-31-16 | D05978J | | 5 | | | | | | SM00202 | | S | 050-099 |
| 251R | 22 | PB | KA | 0-0 | 23-31-16 | D05978J | | 6 | | | | | | SM00201 | | S | 050-099 |
| 252B | 22 | PB | KB | 3-0 | 23-31-16 | D03296 | | 7 | | | | | | SM00202 | | S | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1140

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|-------|------|------|---------|-------------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1146 | 286T1146 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | |
| 252R | 22 | PB | KB | | 0-0 | 23-31-16 | D03296 | | | | 6 | | | SM00201 | S | 050-099 |
| 253B | 22 | PB | KC | | 7-0 | 23-31-16 | SM00202 | | S | | | | | SM00204 | S | 050-099 |
| 253R | 22 | PB | KC | | 0-0 | 23-31-16 | SM00201 | | S | | | | | SM00203 | S | 050-099 |
| 254B | 22 | PB | KD | | 4-0 | 23-31-16 | D03298 | | | 7 | | | | SM00202 | S | 050-099 |
| 254R | 22 | PB | KD | | 0-0 | 23-31-16 | D03298 | | | 6 | | | | SM00201 | S | 050-099 |
| 255B | 22 | PB | KE | | 6-0 | 23-31-16 | SM00204 | | S | | | | | SM00206 | S | 050-099 |
| 255B | 22 | PB | AK | | 7-0 | 23-31-16 | SM00174 | | S | | | | | SM00102 | S | 150-199 |
| 255R | 22 | PB | KE | | 0-0 | 23-31-16 | SM00203 | | S | | | | | SM00205 | S | 050-099 |
| 255R | 22 | PB | AK | | 0-0 | 23-31-16 | SM00175 | | S | | | | | SM00101 | S | 150-199 |
| 256B | 22 | PB | KF | | 3-0 | 23-31-16 | D03300 | | | 7 | | | | SM00204 | S | 050-099 |
| 256B | 22 | PB | AI | | 3-0 | 23-31-16 | D03300 | | | 7 | | | | SM00174 | S | 150-199 |
| 256R | 22 | PB | KF | | 0-0 | 23-31-16 | D03300 | | | 6 | | | | SM00203 | S | 050-099 |
| 256R | 22 | PB | AI | | 0-0 | 23-31-16 | D03300 | | | 6 | | | | SM00175 | S | 150-199 |
| 257B | 22 | PB | KG | | 4-0 | 23-31-16 | D05980P | | | 5 | | | | SM00206 | S | 050-099 |
| 257B | 22 | PB | AJ | | 4-0 | 23-31-16 | D03302 | | | 7 | | | | SM00174 | S | 150-199 |
| 257R | 22 | PB | KG | | 0-0 | 23-31-16 | D05980P | | | 6 | | | | SM00205 | S | 050-099 |
| 257R | 22 | PB | AJ | | 0-0 | 23-31-16 | D03302 | | | 6 | | | | SM00175 | S | 150-199 |
| 258B | 22 | PB | KH | | 4-0 | 23-31-16 | D03302 | | | 7 | | | | SM00204 | S | 050-099 |
| 258R | 22 | PB | KH | | 0-0 | 23-31-16 | D03302 | | | 6 | | | | SM00203 | S | 050-099 |
| 259B | 22 | PB | AD | | 3-0 | 23-31-16 | D05980P | | | 5 | | | | SM00102 | S | 150-199 |
| 259R | 22 | PB | AD | | 0-0 | 23-31-16 | D05980P | | | 6 | | | | SM00101 | S | 150-199 |
| 260B | 22 | PB | KJ | | 3-0 | 23-31-16 | D03378 | | | 7 | | | | SM00206 | S | 050-099 |
| 260B | 22 | PB | AC | | 4-0 | 23-31-16 | D03378 | | | 7 | | | | SM00102 | S | 150-199 |
| 260R | 22 | PB | KJ | | 0-0 | 23-31-16 | D03378 | | | 6 | | | | SM00205 | S | 050-099 |
| 260R | 22 | PB | AC | | 0-0 | 23-31-16 | D03378 | | | 6 | | | | SM00101 | S | 150-199 |
| W1148 | 286T1148 | | | CENTER PSU MOD | | | | | | | | | | | | |
| 001 | 18 | PA | | | 3-0 | 33-24-13 | D05980J | | | 1 | DL | | | SM00001 | S | 050-099, 276-299 |
| 001 | 18 | PA | | | 3-0 | 33-24-13 | D05980J | | | 1 | DL | | | SM00037 | S | 150-199, 275 |
| 002 | 18 | PA | | | 3-0 | 33-24-13 | D05980J | | | 2 | DL | | | SM00002 | S | 050-099, 276-299 |
| 002 | 18 | PA | | | 3-0 | 33-24-13 | D05980J | | | 2 | DL | | | SM00038 | S | 150-199, 275 |
| 003 | 18 | PA | | | 7-0 | 33-24-13 | SM00001 | | | | S | | | SM00003 | S | 050-099, 276-299 |
| 003 | 20 | PA | | | 3-0 | 33-24-13 | D03380 | | | 4 | | | | SM00037 | S | 150-199, 275 |
| 004 | 18 | PA | | | 7-0 | 33-24-13 | SM00002 | | | | S | | | SM00004 | S | 050-099, 276-299 |
| 004 | 20 | PA | | | 3-0 | 33-24-13 | D03380 | | | 3 | | | | SM00038 | S | 150-199 |
| 004 | 20 | PA | | | 2-0 | 33-24-13 | D03380 | | | 3 | | | | SM00038 | S | 275 |
| 005 | 18 | PA | | | 6-0 | 33-24-13 | SM00003 | | | | S | | | SM00005 | S | 050-099, 276-299 |
| 005 | 20 | PA | | | 7-0 | 33-24-13 | D03380 | | | 5 | | | | GD01756 | A.. 2 | 150-199 |
| 005 | 20 | PA | | | 8-0 | 33-24-13 | D03380 | | | 5 | | | | GD01756 | A.. 2 | 275 |

WIRE LIST
D280T132

91-21-11
Section W1140
Page 12
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|--------|-------------|-----|----|--|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | |
| W1148 | 286T1148 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | | | | | |
| 006 | 18 | | PA | 6-0 | 33-24-13 | SM00004 | | | | | S | | | | SM00006 | | S | | | 050-099, 276-299 |
| 006 | 18 | | PA | 7-0 | 33-24-13 | SM00041 | | | | | S | | | | SM00037 | | S | | | 150-199, 275 |
| 007 | 18 | | PA | 4-0 | 33-24-13 | SM00005 | | | | | S | | | | D05982P | 1 | DK | | | 050-099 |
| 007 | 18 | | PA | 7-0 | 33-24-13 | SM00042 | | | | | S | | | | SM00038 | | S | | | 150-199, 275 |
| 007 | 18 | | PA | 4-0 | 33-24-13 | SM00005 | | | | | S | | | | D08186P | 1 | DK | | | 276-299 |
| 008 | 18 | | PA | 4-0 | 33-24-13 | SM00006 | | | | | S | | | | D05982P | 2 | DK | | | 050-099 |
| 008 | 20 | | PA | 4-0 | 33-24-13 | SM00037 | | | | | S | | | | D03382 | 4 | | | | 150-199 |
| 008 | 20 | | PA | 3-0 | 33-24-13 | SM00037 | | | | | S | | | | D03382 | 4 | | | | 275 |
| 008 | 18 | | PA | 4-0 | 33-24-13 | SM00006 | | | | | S | | | | D08186P | 2 | DK | | | 276-299 |
| 009 | 20 | | PA | 4-0 | 33-24-13 | SM00038 | | | | | S | | | | D03382 | 3 | | | | 150-199 |
| 009 | 20 | | PA | 3-0 | 33-24-13 | SM00038 | | | | | S | | | | D03382 | 3 | | | | 275 |
| 010 | 20 | | PA | 5-0 | 33-24-13 | GD01756 | | | A.. | 2 | | | | | D03382 | 5 | | | | 150-199, 275 |
| 013 | 20 | | PA | 3-0 | 33-24-13 | SM00041 | | | | | S | | | | D03384 | 4 | | | | 150-199, 275 |
| 014 | 20 | | PA | 3-0 | 33-24-13 | SM00042 | | | | | S | | | | D03384 | 3 | | | | 150-199, 275 |
| 015 | 20 | | PA | 6-0 | 33-24-13 | GD04906 | | | A.. | 2 | | | | | D03384 | 5 | | | | 150-199 |
| 015 | 20 | | PA | 7-0 | 33-24-13 | GD04906 | | | A.. | 2 | | | | | D03384 | 5 | | | | 275 |
| 016 | 18 | | PA | 7-0 | 33-24-13 | SM00041 | | | | | S | | | | SM00045 | | S | | | 150-199 |
| 016 | 18 | | PA | 5-0 | 33-24-13 | SM00041 | | | | | S | | | | SM00045 | | S | | | 275 |
| 017 | 18 | | PA | 7-0 | 33-24-13 | SM00042 | | | | | S | | | | SM00046 | | S | | | 150-199, 275 |
| 018 | 20 | | PA | 4-0 | 33-24-13 | SM00042 | | | | | S | | | | D03386 | 3 | | | | 150-199 |
| 018 | 20 | | PA | 3-0 | 33-24-13 | SM00042 | | | | | S | | | | D03386 | 3 | | | | 275 |
| 019 | 20 | | PA | 4-0 | 33-24-13 | SM00041 | | | | | S | | | | D03386 | 4 | | | | 150-199 |
| 019 | 20 | | PA | 3-0 | 33-24-13 | SM00041 | | | | | S | | | | D03386 | 4 | | | | 275 |
| 020 | 20 | | PA | 4-0 | 33-24-13 | GD04906 | | | A.. | 2 | | | | | D03386 | 5 | | | | 150-199, 275 |
| 023 | 20 | | PA | 4-0 | 33-24-13 | SM00046 | | | | | S | | | | D03388 | 3 | | | | 150-199 |
| 023 | 20 | | PA | 3-0 | 33-24-13 | SM00046 | | | | | S | | | | D03388 | 3 | | | | 275 |
| 024 | 20 | | PA | 4-0 | 33-24-13 | SM00045 | | | | | S | | | | D03388 | 4 | | | | 150-199 |
| 024 | 20 | | PA | 2-0 | 33-24-13 | SM00045 | | | | | S | | | | D03388 | 4 | | | | 275 |
| 025 | 20 | | PA | 6-0 | 33-24-13 | GD04908 | | | A.. | 2 | | | | | D03388 | 5 | | | | 150-199, 275 |
| 026 | 18 | | PA | 3-0 | 33-24-13 | SM00046 | | | | | S | | | | D08186P | 1 | DK | | | 150-199, 275 |
| 027 | 18 | | PA | 3-0 | 33-24-13 | SM00045 | | | | | S | | | | D08186P | 2 | DK | | | 150-199 |
| 027 | 18 | | PA | 4-0 | 33-24-13 | SM00045 | | | | | S | | | | D08186P | 2 | DK | | | 275 |
| 103 | 22 | | PA | 3-0 | 33-24-13 | SM00002 | | | | | S | | | | D03380 | 3 | | | | 050-099 |
| 103 | 20 | | PA | 3-0 | 33-24-13 | D03380 | | | | 3 | | | | | SM00002 | | S | | | 276-299 |
| 104 | 22 | | PA | 3-0 | 33-24-13 | SM00001 | | | | | S | | | | D03380 | 4 | | | | 050-099 |
| 104 | 20 | | PA | 3-0 | 33-24-13 | D03380 | | | | 4 | | | | | SM00001 | | S | | | 276-299 |
| 105 | 20 | | PA | 8-0 | 33-24-13 | D03380 | | | | 5 | | | | | GD01756 | A.. | 2 | | | 050-099, 276-299 |
| 113 | 22 | | PA | 4-0 | 33-24-13 | SM00002 | | | | | S | | | | D03382 | 3 | | | | 050-099 |
| 113 | 20 | | PA | 4-0 | 33-24-13 | D03382 | | | | 3 | | | | | SM00002 | | S | | | 276-299 |

WIRE LIST

D280T132

91-21-11

Section W1140

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1148 | 286T1148 | | | CENTER PSU MOD (continued) | | | | | | | | | | | |
| 114 | 22 | | | PA | 4-0 | 33-24-13 | SM00001 | | S | | D03382 | 4 | | | 050-099 |
| 114 | 20 | | | PA | 4-0 | 33-24-13 | D03382 | 4 | | | SM00001 | | S | | 276-299 |
| 115 | 20 | | | PA | 6-0 | 33-24-13 | D03382 | 5 | | | GD01756 | A.. | 2 | | 050-099, 276-299 |
| 123 | 22 | | | PA | 3-0 | 33-24-13 | SM00004 | | S | | D03384 | 3 | | | 050-099 |
| 123 | 20 | | | PA | 3-0 | 33-24-13 | D03384 | 3 | | | SM00004 | | S | | 276-299 |
| 124 | 22 | | | PA | 3-0 | 33-24-13 | SM00003 | | S | | D03384 | 4 | | | 050-099 |
| 124 | 20 | | | PA | 3-0 | 33-24-13 | D03384 | 4 | | | SM00003 | | S | | 276-299 |
| 125 | 20 | | | PA | 5-0 | 33-24-13 | D03384 | 5 | | | GD01756 | A.. | 2 | | 050-099 |
| 125 | 20 | | | PA | 7-0 | 33-24-13 | D03384 | 5 | | | GD04906 | A.. | 2 | | 276-299 |
| 133 | 22 | | | PA | 4-0 | 33-24-13 | SM00004 | | S | | D03386 | 3 | | | 050-099 |
| 133 | 20 | | | PA | 4-0 | 33-24-13 | D03386 | 3 | | | SM00004 | | S | | 276-299 |
| 134 | 22 | | | PA | 4-0 | 33-24-13 | SM00003 | | S | | D03386 | 4 | | | 050-099 |
| 134 | 20 | | | PA | 4-0 | 33-24-13 | D03386 | 4 | | | SM00003 | | S | | 276-299 |
| 135 | 20 | | | PA | 5-0 | 33-24-13 | D03386 | 5 | | | GD01764 | A.. | 2 | | 050-099 |
| 135 | 20 | | | PA | 5-0 | 33-24-13 | D03386 | 5 | | | GD04906 | A.. | 2 | | 276-299 |
| 143 | 22 | | | PA | 3-0 | 33-24-13 | SM00006 | | S | | D03388 | 3 | | | 050-099 |
| 143 | 20 | | | PA | 3-0 | 33-24-13 | D03388 | 3 | | | SM00006 | | S | | 276-299 |
| 144 | 22 | | | PA | 3-0 | 33-24-13 | SM00005 | | S | | D03388 | 4 | | | 050-099 |
| 144 | 20 | | | PA | 3-0 | 33-24-13 | D03388 | 4 | | | SM00005 | | S | | 276-299 |
| 145 | 20 | | | PA | 6-0 | 33-24-13 | D03388 | 5 | | | GD01764 | A.. | 2 | | 050-099 |
| 145 | 20 | | | PA | 6-0 | 33-24-13 | D03388 | 5 | | | GD04908 | A.. | 2 | | 276-299 |
| 201B | 22 | | | PB IA | 3-0 | 23-31-16 | D05980J | 3 | | | SM00102 | | S | | 050-099, 276-299 |
| 201B | 22 | | | PB A | 4-0 | 23-31-16 | D05980J | 3 | | | SM00006 | | S | | 150-199 |
| 201B | 22 | | | PB A | 3-0 | 23-31-16 | D05980J | 3 | | | SM00004 | | S | | 275 |
| 201R | 22 | | | PB IA | 0-0 | 23-31-16 | D05980J | 4 | | | SM00101 | | S | | 050-099, 276-299 |
| 201R | 22 | | | PB A | 0-0 | 23-31-16 | D05980J | 4 | | | SM00005 | | S | | 150-199 |
| 201R | 22 | | | PB A | 0-0 | 23-31-16 | D05980J | 4 | | | SM00003 | | S | | 275 |
| 202B | 22 | | | PB IB | 3-0 | 23-31-16 | SM00102 | | S | | D03380 | 2 | | | 050-099 |
| 202B | 22 | | | PB B | 4-0 | 23-31-16 | D08186P | 3 | | | SM00012 | | S | | 150-199, 275 |
| 202B | 22 | | | PB IB | 3-0 | 23-31-16 | D03380 | 2 | | | SM00102 | | S | | 276-299 |
| 202R | 22 | | | PB IB | 0-0 | 23-31-16 | SM00101 | | S | | D03380 | 1 | | | 050-099 |
| 202R | 22 | | | PB B | 0-0 | 23-31-16 | D08186P | 4 | | | SM00011 | | S | | 150-199, 275 |
| 202R | 22 | | | PB IB | 0-0 | 23-31-16 | D03380 | 1 | | | SM00101 | | S | | 276-299 |
| 203B | 22 | | | PB IC | 7-0 | 23-31-16 | SM00102 | | S | | SM00104 | | S | | 050-099, 276-299 |
| 203R | 22 | | | PB IC | 0-0 | 23-31-16 | SM00101 | | S | | SM00103 | | S | | 050-099, 276-299 |
| 204B | 22 | | | PB ID | 4-0 | 23-31-16 | SM00102 | | S | | D03382 | 2 | | | 050-099 |
| 204B | 22 | | | PB C | 4-0 | 23-31-16 | D03380 | 2 | | | SM00006 | | S | | 150-199 |
| 204B | 22 | | | PB C | 3-0 | 23-31-16 | D03380 | 2 | | | SM00004 | | S | | 275 |
| 204B | 22 | | | PB ID | 4-0 | 23-31-16 | D03382 | 2 | | | SM00102 | | S | | 276-299 |

WIRE LIST

D280T132

91-21-11

Section W1140

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|---|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1148 | 286T1148 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | | | |
| 204R | 22 | | PB | ID | 0-0 | 23-31-16 | SM00101 | | | | | | S | D03382 | 1 | | | 050-099 |
| 204R | 22 | | PB | C | 0-0 | 23-31-16 | D03380 | 1 | | | | | | SM00005 | | S | | 150-199 |
| 204R | 22 | | PB | C | 0-0 | 23-31-16 | D03380 | 1 | | | | | | SM00003 | | S | | 275 |
| 204R | 22 | | PB | ID | 0-0 | 23-31-16 | D03382 | 1 | | | | | | SM00101 | | S | | 276-299 |
| 205B | 22 | | PB | IE | 6-0 | 23-31-16 | SM00104 | | | | | | S | SM00106 | | S | | 050-099, 276-299 |
| 205B | 22 | | PB | D | 7-0 | 23-31-16 | SM00008 | | | | | | | SM00004 | | S | | 275 |
| 205R | 22 | | PB | IE | 0-0 | 23-31-16 | SM00103 | | | | | | | SM00105 | | S | | 050-099, 276-299 |
| 205R | 22 | | PB | D | 0-0 | 23-31-16 | SM00007 | | | | | | | SM00003 | | S | | 275 |
| 206B | 22 | | PB | IF | 3-0 | 23-31-16 | SM00104 | | | | | | | D03384 | 2 | | | 050-099 |
| 206B | 22 | | PB | E | 3-0 | 23-31-16 | D03382 | 2 | | | | | | SM00006 | | S | | 150-199 |
| 206B | 22 | | PB | E | 3-0 | 23-31-16 | D03382 | 2 | | | | | | SM00004 | | S | | 275 |
| 206B | 22 | | PB | IF | 3-0 | 23-31-16 | D03384 | 2 | | | | | | SM00104 | | S | | 276-299 |
| 206R | 22 | | PB | IF | 0-0 | 23-31-16 | SM00103 | | | | | | S | D03384 | 1 | | | 050-099 |
| 206R | 22 | | PB | E | 0-0 | 23-31-16 | D03382 | 1 | | | | | | SM00005 | | S | | 150-199 |
| 206R | 22 | | PB | E | 0-0 | 23-31-16 | D03382 | 1 | | | | | | SM00003 | | S | | 275 |
| 206R | 22 | | PB | IF | 0-0 | 23-31-16 | D03384 | 1 | | | | | | SM00103 | | S | | 276-299 |
| 207B | 22 | | PB | IG | 4-0 | 23-31-16 | SM00106 | | | | | | S | D05982P | 3 | | | 050-099 |
| 207B | 22 | | PB | F | 8-0 | 23-31-16 | SM00006 | | | | | | S | SM00010 | | S | | 150-199 |
| 207B | 22 | | PB | IG | 4-0 | 23-31-16 | SM00106 | | | | | | S | D08186P | 3 | | | 276-299 |
| 207R | 22 | | PB | IG | 0-0 | 23-31-16 | SM00105 | | | | | | S | D05982P | 4 | | | 050-099 |
| 207R | 22 | | PB | F | 0-0 | 23-31-16 | SM00005 | | | | | | S | SM00009 | | S | | 150-199 |
| 207R | 22 | | PB | IG | 0-0 | 23-31-16 | SM00105 | | | | | | S | D08186P | 4 | | | 276-299 |
| 208B | 22 | | PB | IH | 4-0 | 23-31-16 | SM00104 | | | | | | S | D03386 | 2 | | | 050-099 |
| 208B | 22 | | PB | G | 5-0 | 23-31-16 | D03384 | 2 | | | | | | SM00010 | | S | | 150-199 |
| 208B | 22 | | PB | G | 3-0 | 23-31-16 | D03384 | 2 | | | | | | SM00008 | | S | | 275 |
| 208B | 22 | | PB | IH | 4-0 | 23-31-16 | D03386 | 2 | | | | | | SM00104 | | S | | 276-299 |
| 208R | 22 | | PB | IH | 0-0 | 23-31-16 | SM00103 | | | | | | S | D03386 | 1 | | | 050-099 |
| 208R | 22 | | PB | G | 0-0 | 23-31-16 | D03384 | 1 | | | | | | SM00009 | | S | | 150-199 |
| 208R | 22 | | PB | G | 0-0 | 23-31-16 | D03384 | 1 | | | | | | SM00007 | | S | | 275 |
| 208R | 22 | | PB | IH | 0-0 | 23-31-16 | D03386 | 1 | | | | | | SM00103 | | S | | 276-299 |
| 209B | 22 | | PB | H | 7-0 | 23-31-16 | SM00008 | | | | | | S | SM00012 | | S | | 275 |
| 209R | 22 | | PB | H | 0-0 | 23-31-16 | SM00007 | | | | | | S | SM00011 | | S | | 275 |
| 210B | 22 | | PB | IJ | 3-0 | 23-31-16 | SM00106 | | | | | | S | D03388 | 2 | | | 050-099 |
| 210B | 22 | | PB | I | 3-0 | 23-31-16 | D03386 | 2 | | | | | | SM00010 | | S | | 150-199 |
| 210B | 22 | | PB | I | 4-0 | 23-31-16 | D03386 | 2 | | | | | | SM00008 | | S | | 275 |
| 210B | 22 | | PB | IJ | 3-0 | 23-31-16 | D03388 | 2 | | | | | | SM00106 | | S | | 276-299 |
| 210R | 22 | | PB | IJ | 0-0 | 23-31-16 | SM00105 | | | | | | S | D03388 | 1 | | | 050-099 |
| 210R | 22 | | PB | I | 0-0 | 23-31-16 | D03386 | 1 | | | | | | SM00009 | | S | | 150-199 |
| 210R | 22 | | PB | I | 0-0 | 23-31-16 | D03386 | 1 | | | | | | SM00007 | | S | | 275 |

WIRE LIST

D280T132

91-21-11

Section W1140

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1148 | 286T1148 | | | CENTER PSU MOD (continued) | | | | | | | | | | | |
| 210R | 22 | PB | IJ | | 0-0 | 23-31-16 | D03388 | | | | SM00105 | | | | 276-299 |
| 211B | 22 | PB | J | | 5-0 | 23-31-16 | SM00010 | | S | | SM00012 | | | | 150-199 |
| 211R | 22 | PB | J | | 0-0 | 23-31-16 | SM00009 | | | S | SM00011 | | | | 150-199 |
| 212B | 22 | PB | K | | 4-0 | 23-31-16 | D03388 | | 2 | | SM00012 | | | | 150-199 |
| 212B | 22 | PB | K | | 3-0 | 23-31-16 | D03388 | | 2 | | SM00012 | | | | 275 |
| 212R | 22 | PB | K | | 0-0 | 23-31-16 | D03388 | | 1 | | SM00011 | | | | 150-199, 275 |
| 221B | 22 | PB | AA | | 3-0 | 23-31-16 | D05980J | | 5 | | SM00104 | | | | 150-199 |
| 221R | 22 | PB | AA | | 0-0 | 23-31-16 | D05980J | | 6 | | SM00103 | | | | 150-199 |
| 222B | 22 | PB | AB | | 3-0 | 23-31-16 | D08186P | | 5 | | SM00112 | | | | 150-199 |
| 222R | 22 | PB | AB | | 0-0 | 23-31-16 | D08186P | | 6 | | SM00111 | | | | 150-199 |
| 224B | 22 | PB | AC | | 3-0 | 23-31-16 | D03380 | | 7 | | SM00104 | | | | 150-199 |
| 224R | 22 | PB | AC | | 0-0 | 23-31-16 | D03380 | | 6 | | SM00103 | | | | 150-199 |
| 225B | 22 | PB | AD | | 7-0 | 23-31-16 | SM00107 | | | S | SM00104 | | | | 150-199 |
| 225R | 22 | PB | AD | | 0-0 | 23-31-16 | SM00108 | | | S | SM00103 | | | | 150-199 |
| 226B | 22 | PB | AE | | 4-0 | 23-31-16 | D03382 | | 7 | | SM00104 | | | | 150-199 |
| 226R | 22 | PB | AE | | 0-0 | 23-31-16 | D03382 | | 6 | | SM00103 | | | | 150-199 |
| 228B | 22 | PB | AG | | 3-0 | 23-31-16 | D03384 | | 7 | | SM00107 | | | | 150-199 |
| 228R | 22 | PB | AG | | 0-0 | 23-31-16 | D03384 | | 6 | | SM00108 | | | | 150-199 |
| 229B | 22 | PB | AH | | 7-0 | 23-31-16 | SM00107 | | | S | SM00112 | | | | 150-199 |
| 229R | 22 | PB | AH | | 0-0 | 23-31-16 | SM00108 | | | S | SM00111 | | | | 150-199 |
| 230B | 22 | PB | AI | | 4-0 | 23-31-16 | D03386 | | 7 | | SM00107 | | | | 150-199 |
| 230R | 22 | PB | AI | | 0-0 | 23-31-16 | D03386 | | 6 | | SM00108 | | | | 150-199 |
| 232B | 22 | PB | AK | | 4-0 | 23-31-16 | D03388 | | 7 | | SM00112 | | | | 150-199 |
| 232R | 22 | PB | AK | | 0-0 | 23-31-16 | D03388 | | 6 | | SM00111 | | | | 150-199 |
| 251B | 22 | PB | KA | | 3-0 | 23-31-16 | D05980J | | 5 | | SM00202 | | | | 050-099 |
| 251R | 22 | PB | KA | | 0-0 | 23-31-16 | D05980J | | 6 | | SM00201 | | | | 050-099 |
| 252B | 22 | PB | KB | | 3-0 | 23-31-16 | D03380 | | 7 | | SM00202 | | | | 050-099 |
| 252R | 22 | PB | KB | | 0-0 | 23-31-16 | D03380 | | 6 | | SM00201 | | | | 050-099 |
| 253B | 22 | PB | KC | | 7-0 | 23-31-16 | SM00202 | | | S | SM00204 | | | | 050-099 |
| 253R | 22 | PB | KC | | 0-0 | 23-31-16 | SM00201 | | | S | SM00203 | | | | 050-099 |
| 254B | 22 | PB | KD | | 4-0 | 23-31-16 | D03382 | | 7 | | SM00202 | | | | 050-099 |
| 254R | 22 | PB | KD | | 0-0 | 23-31-16 | D03382 | | 6 | | SM00201 | | | | 050-099 |
| 255B | 22 | PB | KE | | 6-0 | 23-31-16 | SM00204 | | | S | SM00206 | | | | 050-099 |
| 255R | 22 | PB | KE | | 0-0 | 23-31-16 | SM00203 | | | S | SM00205 | | | | 050-099 |
| 256B | 22 | PB | KF | | 3-0 | 23-31-16 | D03384 | | 7 | | SM00204 | | | | 050-099 |
| 256R | 22 | PB | KF | | 0-0 | 23-31-16 | D03384 | | 6 | | SM00203 | | | | 050-099 |
| 257B | 22 | PB | KG | | 4-0 | 23-31-16 | SM00206 | | | S | D05982P | | 5 | | 050-099 |
| 257R | 22 | PB | KG | | 0-0 | 23-31-16 | SM00205 | | | S | D05982P | | 6 | | 050-099 |
| 258B | 22 | PB | KH | | 4-0 | 23-31-16 | D03386 | | 7 | | SM00204 | | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1140

Page 16

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1148 | 286T1148 | | | CENTER PSU MOD (continued) | | | | | | | | | | | |
| 258R | 22 | PB | KH | | 0-0 | 23-31-16 | D03386 | | 6 | | SM00203 | | S | | 050-099 |
| 260B | 22 | PB | KJ | | 3-0 | 23-31-16 | D03388 | | 7 | | SM00206 | | S | | 050-099 |
| 260R | 22 | PB | KJ | | 0-0 | 23-31-16 | D03388 | | 6 | | SM00205 | | S | | 050-099 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-----------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1150 | 286T1150 | | | CENTRE PSU MOD | | | | | | | | | | | |
| 001 | 18 | | PA | | 3-0 | 33-24-13 | D05982J | 1 | DL | | SM00001 | | S | | 050-099, 276-299 |
| 001 | 18 | | PA | | 4-0 | 33-24-13 | D05982J | 1 | DL | | SM00048 | | S | | 150-199 |
| 001 | 18 | | PA | | 3-0 | 33-24-13 | D05982J | 1 | DL | | SM00048 | | S | | 275 |
| 002 | 18 | | PA | | 3-0 | 33-24-13 | D05982J | 2 | DL | | SM00002 | | S | | 050-099, 276-299 |
| 002 | 18 | | PA | | 4-0 | 33-24-13 | D05982J | 2 | DL | | SM00047 | | S | | 150-199 |
| 002 | 18 | | PA | | 3-0 | 33-24-13 | D05982J | 2 | DL | | SM00047 | | S | | 275 |
| 003 | 18 | | PA | | 7-0 | 33-24-13 | SM00001 | | S | | SM00003 | | S | | 050-099, 276-299 |
| 003 | 20 | | PA | | 4-0 | 33-24-13 | D03390 | 3 | | | SM00048 | | S | | 150-199 |
| 003 | 20 | | PA | | 3-0 | 33-24-13 | D03390 | 3 | | | SM00048 | | S | | 275 |
| 004 | 18 | | PA | | 7-0 | 33-24-13 | SM00002 | | S | | SM00004 | | S | | 050-099, 276-299 |
| 004 | 20 | | PA | | 4-0 | 33-24-13 | D03390 | 4 | | | SM00047 | | S | | 150-199 |
| 004 | 20 | | PA | | 3-0 | 33-24-13 | D03390 | 4 | | | SM00047 | | S | | 275 |
| 005 | 18 | | PA | | 6-0 | 33-24-13 | SM00003 | | S | | SM00005 | | S | | 050-099, 276-299 |
| 005 | 20 | | PA | | 7-0 | 33-24-13 | D03390 | 5 | | | GD04674 | A.. | 2 | | 150-199 |
| 005 | 20 | | PA | | 8-0 | 33-24-13 | D03390 | 5 | | | GD04674 | A.. | 2 | | 275 |
| 006 | 18 | | PA | | 6-0 | 33-24-13 | SM00004 | | S | | SM00006 | | S | | 050-099, 276-299 |
| 006 | 18 | | PA | | 7-0 | 33-24-13 | SM00052 | | S | | SM00048 | | S | | 150-199, 275 |
| 007 | 18 | | PA | | 4-0 | 33-24-13 | SM00005 | | S | | D05984P | 1 | DK | | 050-099, 276-299 |
| 007 | 18 | | PA | | 7-0 | 33-24-13 | SM00051 | | S | | SM00047 | | S | | 150-199, 275 |
| 008 | 18 | | PA | | 4-0 | 33-24-13 | SM00006 | | S | | D05984P | 2 | DK | | 050-099, 276-299 |
| 008 | 20 | | PA | | 4-0 | 33-24-13 | SM00048 | | S | | D03392 | 3 | | | 150-199, 275 |
| 009 | 20 | | PA | | 4-0 | 33-24-13 | SM00047 | | S | | D03392 | 4 | | | 150-199, 275 |
| 010 | 20 | | PA | | 5-0 | 33-24-13 | GD04674 | A.. | 2 | | D03392 | 5 | | | 150-199 |
| 010 | 20 | | PA | | 6-0 | 33-24-13 | GD04674 | A.. | 2 | | D03392 | 5 | | | 275 |
| 013 | 20 | | PA | | 3-0 | 33-24-13 | D03394 | 3 | | | SM00052 | | S | | 150-199, 275 |
| 014 | 20 | | PA | | 3-0 | 33-24-13 | D03394 | 4 | | | SM00051 | | S | | 150-199, 275 |
| 015 | 20 | | PA | | 5-0 | 33-24-13 | D03394 | 5 | | | GD04674 | A.. | 2 | | 150-199, 275 |
| 016 | 18 | | PA | | 7-0 | 33-24-13 | SM00056 | | S | | SM00052 | | S | | 150-199, 275 |
| 017 | 18 | | PA | | 7-0 | 33-24-13 | SM00055 | | S | | SM00051 | | S | | 150-199, 275 |
| 018 | 20 | | PA | | 3-0 | 33-24-13 | SM00052 | | S | | D03396 | 3 | | | 150-199 |
| 018 | 20 | | PA | | 4-0 | 33-24-13 | SM00052 | | S | | D03396 | 3 | | | 275 |
| 019 | 20 | | PA | | 3-0 | 33-24-13 | SM00051 | | S | | D03396 | 4 | | | 150-199 |
| 019 | 20 | | PA | | 4-0 | 33-24-13 | SM00051 | | S | | D03396 | 4 | | | 275 |
| 020 | 20 | | PA | | 5-0 | 33-24-13 | GD01774 | A.. | 2 | | D03396 | 5 | | | 150-199, 275 |
| 023 | 20 | | PA | | 4-0 | 33-24-13 | SM00055 | | S | | D03398 | 4 | | | 150-199 |
| 023 | 20 | | PA | | 3-0 | 33-24-13 | SM00055 | | S | | D03398 | 4 | | | 275 |
| 024 | 20 | | PA | | 4-0 | 33-24-13 | SM00056 | | S | | D03398 | 3 | | | 150-199 |
| 024 | 20 | | PA | | 3-0 | 33-24-13 | SM00056 | | S | | D03398 | 3 | | | 275 |
| 025 | 20 | | PA | | 6-0 | 33-24-13 | GD01774 | A.. | 2 | | D03398 | 5 | | | 150-199, 275 |

WIRE LIST

D280T132

91-21-11

Section W1150

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|--------|-------------|-----|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W1150 | 286T1150 | | | CENTRE PSU MOD (continued) | | | | | | | | | | | | | | | |
| 026 | 18 | | PA | | 4-0 | 33-24-13 | SM00055 | | | | | | | S | D05984P | 1 | DK | | 150-199, 275 |
| 027 | 18 | | PA | | 3-0 | 33-24-13 | SM00056 | | | | | | | S | D05984P | 2 | DK | | 150-199 |
| 027 | 18 | | PA | | 4-0 | 33-24-13 | SM00056 | | | | | | | S | D05984P | 2 | DK | | 275 |
| 103 | 22 | | PA | | 3-0 | 33-24-13 | SM00002 | | | | | | | S | D03390 | 3 | | | 050-099 |
| 103 | 20 | | PA | | 3-0 | 33-24-13 | D03390 | | 3 | | | | | | SM00002 | | S | | 276-299 |
| 104 | 22 | | PA | | 3-0 | 33-24-13 | SM00001 | | | | | | | S | D03390 | 4 | | | 050-099 |
| 104 | 20 | | PA | | 3-0 | 33-24-13 | D03390 | | 4 | | | | | | SM00001 | | S | | 276-299 |
| 105 | 20 | | PA | | 4-0 | 33-24-13 | D03390 | | 5 | | | | | | GD01760 | A.. | 2 | | 050-099 |
| 105 | 20 | | PA | | 8-0 | 33-24-13 | D03390 | | 5 | | | | | | GD04674 | A.. | 2 | | 276-299 |
| 113 | 22 | | PA | | 4-0 | 33-24-13 | SM00002 | | | | | | | S | D03392 | 3 | | | 050-099 |
| 113 | 20 | | PA | | 4-0 | 33-24-13 | D03392 | | 3 | | | | | | SM00002 | | S | | 276-299 |
| 114 | 22 | | PA | | 4-0 | 33-24-13 | SM00001 | | | | | | | S | D03392 | 4 | | | 050-099 |
| 114 | 20 | | PA | | 4-0 | 33-24-13 | D03392 | | 4 | | | | | | SM00001 | | S | | 276-299 |
| 115 | 20 | | PA | | 10-0 | 33-24-13 | D03392 | | 5 | | | | | | GD01774 | A.. | 2 | | 050-099 |
| 115 | 20 | | PA | | 6-0 | 33-24-13 | D03392 | | 5 | | | | | | GD04674 | A.. | 2 | | 276-299 |
| 123 | 22 | | PA | | 3-0 | 33-24-13 | SM00004 | | | | | | | S | D03394 | 3 | | | 050-099 |
| 123 | 20 | | PA | | 3-0 | 33-24-13 | D03394 | | 3 | | | | | | SM00004 | | S | | 276-299 |
| 124 | 22 | | PA | | 3-0 | 33-24-13 | SM00003 | | | | | | | S | D03394 | 4 | | | 050-099 |
| 124 | 20 | | PA | | 3-0 | 33-24-13 | D03394 | | 4 | | | | | | SM00003 | | S | | 276-299 |
| 125 | 20 | | PA | | 7-0 | 33-24-13 | D03394 | | 5 | | | | | | GD01774 | A.. | 2 | | 050-099 |
| 125 | 20 | | PA | | 6-0 | 33-24-13 | D03394 | | 5 | | | | | | GD04674 | A.. | 2 | | 276-299 |
| 133 | 22 | | PA | | 4-0 | 33-24-13 | SM00004 | | | | | | | S | D03396 | 3 | | | 050-099 |
| 133 | 20 | | PA | | 4-0 | 33-24-13 | D03396 | | 3 | | | | | | SM00004 | | S | | 276-299 |
| 134 | 22 | | PA | | 4-0 | 33-24-13 | SM00003 | | | | | | | S | D03396 | 4 | | | 050-099 |
| 134 | 20 | | PA | | 4-0 | 33-24-13 | D03396 | | 4 | | | | | | SM00003 | | S | | 276-299 |
| 135 | 20 | | PA | | 5-0 | 33-24-13 | D03396 | | 5 | | | | | | GD01774 | A.. | 2 | | 050-099, 276-299 |
| 143 | 22 | | PA | | 3-0 | 33-24-13 | SM00006 | | | | | | | S | D03398 | 3 | | | 050-099 |
| 143 | 20 | | PA | | 3-0 | 33-24-13 | D03398 | | 3 | | | | | | SM00006 | | S | | 276-299 |
| 144 | 22 | | PA | | 3-0 | 33-24-13 | SM00005 | | | | | | | S | D03398 | 4 | | | 050-099 |
| 144 | 20 | | PA | | 3-0 | 33-24-13 | D03398 | | 4 | | | | | | SM00005 | | S | | 276-299 |
| 145 | 20 | | PA | | 6-0 | 33-24-13 | D03398 | | 5 | | | | | | GD01774 | A.. | 2 | | 050-099, 276-299 |
| 201B | 22 | | PB | IA | 3-0 | 23-31-16 | D05982J | | 3 | | | | | | SM00102 | | S | | 050-099 |
| 201B | 22 | | PB | IA | 3-0 | 23-31-16 | SM00102 | | | | | | | S | D05982J | 3 | | | 276-299 |
| 201R | 22 | | PB | IA | 0-0 | 23-31-16 | D05982J | | 4 | | | | | | SM00101 | | S | | 050-099 |
| 201R | 22 | | PB | IA | 0-0 | 23-31-16 | SM00101 | | | | | | | S | D05982J | 4 | | | 276-299 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-16 | SM00102 | | | | | | | S | D03390 | 2 | | | 050-099 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-16 | D03390 | | 2 | | | | | | SM00102 | | S | | 276-299 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-16 | SM00101 | | | | | | | S | D03390 | 1 | | | 050-099 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-16 | D03390 | | 1 | | | | | | SM00101 | | S | | 276-299 |

WIRE LIST

D280T132

91-21-11

Section W1150

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1150 | 286T1150 | | | CENTRE PSU MOD (continued) | | | | | | | | | | | | | |
| 203B | 22 | PB | IC | 7-0 | 23-31-16 | SM00102 | | | | S | | | | SM00104 | | S | 050-099, 276-299 |
| 203R | 22 | PB | IC | 0-0 | 23-31-16 | SM00101 | | | | S | | | | SM00103 | | S | 050-099, 276-299 |
| 204B | 22 | PB | ID | 4-0 | 23-31-16 | SM00102 | | | | S | | | | D03392 | 2 | | 050-099 |
| 204B | 22 | PB | ID | 4-0 | 23-31-16 | D03392 | | | 2 | | | | | SM00102 | | S | 276-299 |
| 204R | 22 | PB | ID | 0-0 | 23-31-16 | SM00101 | | | | S | | | | D03392 | 1 | | 050-099 |
| 204R | 22 | PB | ID | 0-0 | 23-31-16 | D03392 | | | 1 | | | | | SM00101 | | S | 276-299 |
| 205B | 22 | PB | IE | 6-0 | 23-31-16 | SM00104 | | | | S | | | | SM00106 | | S | 050-099, 276-299 |
| 205R | 22 | PB | IE | 0-0 | 23-31-16 | SM00103 | | | | S | | | | SM00105 | | S | 050-099, 276-299 |
| 206B | 22 | PB | IF | 3-0 | 23-31-16 | SM00104 | | | | S | | | | D03394 | 2 | | 050-099 |
| 206B | 22 | PB | IF | 3-0 | 23-31-16 | D03394 | | | 2 | | | | | SM00104 | | S | 276-299 |
| 206R | 22 | PB | IF | 0-0 | 23-31-16 | SM00103 | | | | S | | | | D03394 | 1 | | 050-099 |
| 206R | 22 | PB | IF | 0-0 | 23-31-16 | D03394 | | | 1 | | | | | SM00103 | | S | 276-299 |
| 207B | 22 | PB | IG | 4-0 | 23-31-16 | SM00106 | | | | S | | | | D05984P | 3 | | 050-099, 276-299 |
| 207R | 22 | PB | IG | 0-0 | 23-31-16 | SM00105 | | | | S | | | | D05984P | 4 | | 050-099, 276-299 |
| 208B | 22 | PB | IH | 4-0 | 23-31-16 | SM00104 | | | | S | | | | D03396 | 2 | | 050-099 |
| 208B | 22 | PB | IH | 4-0 | 23-31-16 | D03396 | | | 2 | | | | | SM00104 | | S | 276-299 |
| 208R | 22 | PB | IH | 0-0 | 23-31-16 | SM00103 | | | | S | | | | D03396 | 1 | | 050-099 |
| 208R | 22 | PB | IH | 0-0 | 23-31-16 | D03396 | | | 1 | | | | | SM00103 | | S | 276-299 |
| 210B | 22 | PB | IJ | 3-0 | 23-31-16 | SM00106 | | | | S | | | | D03398 | 2 | | 050-099 |
| 210B | 22 | PB | IJ | 3-0 | 23-31-16 | D03398 | | | 2 | | | | | SM00106 | | S | 276-299 |
| 210R | 22 | PB | IJ | 0-0 | 23-31-16 | SM00105 | | | | S | | | | D03398 | 1 | | 050-099 |
| 210R | 22 | PB | IJ | 0-0 | 23-31-16 | D03398 | | | 1 | | | | | SM00105 | | S | 276-299 |
| 213B | 22 | PB | A | 6-0 | 23-31-16 | D05982J | | | 3 | | | | | SM00016 | | S | 150-199 |
| 213B | 22 | PB | A | 3-0 | 23-31-16 | D05982J | | | 3 | | | | | SM00014 | | S | 275 |
| 213R | 22 | PB | A | 0-0 | 23-31-16 | D05982J | | | 4 | | | | | SM00015 | | S | 150-199 |
| 213R | 22 | PB | A | 0-0 | 23-31-16 | D05982J | | | 4 | | | | | SM00013 | | S | 275 |
| 214B | 22 | PB | B | 6-0 | 23-31-16 | D03390 | | | 2 | | | | | SM00016 | | S | 150-199 |
| 214B | 22 | PB | B | 3-0 | 23-31-16 | D03390 | | | 2 | | | | | SM00014 | | S | 275 |
| 214R | 22 | PB | B | 0-0 | 23-31-16 | D03390 | | | 1 | | | | | SM00015 | | S | 150-199 |
| 214R | 22 | PB | B | 0-0 | 23-31-16 | D03390 | | | 1 | | | | | SM00013 | | S | 275 |
| 215B | 22 | PB | C | 7-0 | 23-31-16 | SM00014 | | | | S | | | | SM00020 | | S | 275 |
| 215R | 22 | PB | C | 0-0 | 23-31-16 | SM00013 | | | | S | | | | SM00019 | | S | 275 |
| 216B | 22 | PB | D | 3-0 | 23-31-16 | D03392 | | | 2 | | | | | SM00016 | | S | 150-199 |
| 216B | 22 | PB | D | 4-0 | 23-31-16 | D03392 | | | 2 | | | | | SM00014 | | S | 275 |
| 216R | 22 | PB | D | 0-0 | 23-31-16 | D03392 | | | 1 | | | | | SM00015 | | S | 150-199 |
| 216R | 22 | PB | D | 0-0 | 23-31-16 | D03392 | | | 1 | | | | | SM00013 | | S | 275 |
| 217B | 22 | PB | E | 7-0 | 23-31-16 | SM00016 | | | | S | | | | SM00020 | | S | 150-199 |
| 217R | 22 | PB | E | 0-0 | 23-31-16 | SM00015 | | | | S | | | | SM00019 | | S | 150-199 |
| 218B | 22 | PB | F | 6-0 | 23-31-16 | D03394 | | | 2 | | | | | SM00020 | | S | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1150

Page 3

Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|-----------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|--------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1150 | 286T1150 | | | CENTRE PSU MOD (continued) | | | | | | | | | | | | | |
| 218B | 22 | PB | F | 3-0 | 23-31-16 | D03394 | | 2 | | | | | SM00020 | | S | | 275 |
| 218R | 22 | PB | F | 0-0 | 23-31-16 | D03394 | | 1 | | | | | SM00019 | | S | | 150-199, 275 |
| 220B | 22 | PB | H | 4-0 | 23-31-16 | D03396 | | 2 | | | | | SM00020 | | S | | 150-199, 275 |
| 220R | 22 | PB | H | 0-0 | 23-31-16 | D03396 | | 1 | | | | | SM00019 | | S | | 150-199, 275 |
| 221B | 22 | PB | I | 5-0 | 23-31-16 | SM00020 | | | | | S | | SM00022 | | S | | 150-199 |
| 221B | 22 | PB | I | 7-0 | 23-31-16 | SM00020 | | | | | S | | SM00022 | | S | | 275 |
| 221R | 22 | PB | I | 0-0 | 23-31-16 | SM00019 | | | | | S | | SM00021 | | S | | 150-199, 275 |
| 222B | 22 | PB | J | 4-0 | 23-31-16 | D03398 | | 2 | | | | | SM00022 | | S | | 150-199 |
| 222B | 22 | PB | J | 3-0 | 23-31-16 | D03398 | | 2 | | | | | SM00022 | | S | | 275 |
| 222R | 22 | PB | J | 0-0 | 23-31-16 | D03398 | | 1 | | | | | SM00021 | | S | | 150-199, 275 |
| 223B | 22 | PB | K | 3-0 | 23-31-16 | D05984P | | 3 | | | | | SM00022 | | S | | 150-199 |
| 223B | 22 | PB | K | 4-0 | 23-31-16 | D05984P | | 3 | | | | | SM00022 | | S | | 275 |
| 223R | 22 | PB | K | 0-0 | 23-31-16 | D05984P | | 4 | | | | | SM00021 | | S | | 150-199, 275 |
| 251B | 22 | PB | KA | 3-0 | 23-31-16 | D05982J | | 5 | | | | | SM00202 | | S | | 050-099 |
| 251R | 22 | PB | KA | 0-0 | 23-31-16 | D05982J | | 6 | | | | | SM00201 | | S | | 050-099 |
| 252B | 22 | PB | KB | 3-0 | 23-31-16 | D03390 | | 7 | | | | | SM00202 | | S | | 050-099 |
| 252R | 22 | PB | KB | 0-0 | 23-31-16 | D03390 | | 6 | | | | | SM00201 | | S | | 050-099 |
| 253B | 22 | PB | KC | 7-0 | 23-31-16 | SM00202 | | | | | S | | SM00204 | | S | | 050-099 |
| 253B | 22 | PB | AA | 3-0 | 23-31-16 | D05982J | | 5 | | | | | SM00114 | | S | | 150-199 |
| 253R | 22 | PB | KC | 0-0 | 23-31-16 | SM00201 | | | | | S | | SM00203 | | S | | 050-099 |
| 253R | 22 | PB | AA | 0-0 | 23-31-16 | D05982J | | 6 | | | | | SM00113 | | S | | 150-199 |
| 254B | 22 | PB | KD | 4-0 | 23-31-16 | D03392 | | 7 | | | | | SM00202 | | S | | 050-099 |
| 254B | 22 | PB | AB | 3-0 | 23-31-16 | D03390 | | 7 | | | | | SM00114 | | S | | 150-199 |
| 254R | 22 | PB | KD | 0-0 | 23-31-16 | D03392 | | 6 | | | | | SM00201 | | S | | 050-099 |
| 254R | 22 | PB | AB | 0-0 | 23-31-16 | D03390 | | 6 | | | | | SM00113 | | S | | 150-199 |
| 255B | 22 | PB | KE | 6-0 | 23-31-16 | SM00204 | | | | | S | | SM00206 | | S | | 050-099 |
| 255B | 22 | PB | AC | 7-0 | 23-31-16 | SM00114 | | | | | S | | SM00118 | | S | | 150-199 |
| 255R | 22 | PB | KE | 0-0 | 23-31-16 | SM00203 | | | | | S | | SM00205 | | S | | 050-099 |
| 255R | 22 | PB | AC | 0-0 | 23-31-16 | SM00113 | | | | | S | | SM00117 | | S | | 150-199 |
| 256B | 22 | PB | KF | 3-0 | 23-31-16 | D03394 | | 7 | | | | | SM00204 | | S | | 050-099 |
| 256B | 22 | PB | AD | 4-0 | 23-31-16 | D03392 | | 7 | | | | | SM00114 | | S | | 150-199 |
| 256R | 22 | PB | KF | 0-0 | 23-31-16 | D03394 | | 6 | | | | | SM00203 | | S | | 050-099 |
| 256R | 22 | PB | AD | 0-0 | 23-31-16 | D03392 | | 6 | | | | | SM00113 | | S | | 150-199 |
| 257B | 22 | PB | KG | 4-0 | 23-31-16 | SM00206 | | | | | S | | D05984P | | 5 | | 050-099 |
| 257R | 22 | PB | KG | 0-0 | 23-31-16 | SM00205 | | | | | S | | D05984P | | 6 | | 050-099 |
| 258B | 22 | PB | KH | 4-0 | 23-31-16 | D03396 | | 7 | | | | | SM00204 | | S | | 050-099 |
| 258B | 22 | PB | AF | 3-0 | 23-31-16 | D03394 | | 7 | | | | | SM00118 | | S | | 150-199 |
| 258R | 22 | PB | KH | 0-0 | 23-31-16 | D03396 | | 6 | | | | | SM00203 | | S | | 050-099 |
| 258R | 22 | PB | AF | 0-0 | 23-31-16 | D03394 | | 6 | | | | | SM00117 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1150

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1150 | 286T1150 | | | CENTRE PSU MOD (continued) | | | | | | | | | | | |
| 259B | 22 | PB | AG | | 7-0 | 23-31-16 | SM00118 | | | | SM00122 | | S | | 150-199 |
| 259R | 22 | PB | AG | | 0-0 | 23-31-16 | SM00117 | | | | SM00121 | | S | | 150-199 |
| 260B | 22 | PB | KJ | | 3-0 | 23-31-16 | D03398 | | 7 | | SM00206 | | S | | 050-099 |
| 260B | 22 | PB | AH | | 3-0 | 23-31-16 | D03396 | | 7 | | SM00118 | | S | | 150-199 |
| 260R | 22 | PB | KJ | | 0-0 | 23-31-16 | D03398 | | 6 | | SM00205 | | S | | 050-099 |
| 260R | 22 | PB | AH | | 0-0 | 23-31-16 | D03396 | | 6 | | SM00117 | | S | | 150-199 |
| 262B | 22 | PB | AJ | | 4-0 | 23-31-16 | D03398 | | 7 | | SM00122 | | S | | 150-199 |
| 262R | 22 | PB | AJ | | 0-0 | 23-31-16 | D03398 | | 6 | | SM00121 | | S | | 150-199 |
| 263B | 22 | PB | AK | | 3-0 | 23-31-16 | D05984P | | 5 | | SM00122 | | S | | 150-199 |
| 263R | 22 | PB | AK | | 0-0 | 23-31-16 | D05984P | | 6 | | SM00121 | | S | | 150-199 |
| W1152 | 286T1152 | | | CENTER PSU MOD | | | | | | | | | | | |
| 001 | 18 | PA | | | 3-0 | 33-24-13 | D05984J | | 1 | DL | SM00001 | | S | | 050-099, 276-299 |
| 001 | 18 | PA | | | 3-0 | 33-24-13 | D05984J | | 1 | DL | SM00057 | | S | | 150-199 |
| 001 | 18 | PA | | | 2-0 | 33-24-13 | D05984J | | 1 | DL | SM00057 | | S | | 275 |
| 002 | 18 | PA | | | 3-0 | 33-24-13 | D05984J | | 2 | DL | SM00002 | | S | | 050-099, 276-299 |
| 002 | 18 | PA | | | 3-0 | 33-24-13 | D05984J | | 2 | DL | SM00058 | | S | | 150-199 |
| 002 | 18 | PA | | | 2-0 | 33-24-13 | D05984J | | 2 | DL | SM00058 | | S | | 275 |
| 003 | 20 | PA | | | 3-0 | 33-24-13 | D03400 | | 4 | | SM00057 | | S | | 150-199 |
| 003 | 20 | PA | | | 2-0 | 33-24-13 | D03400 | | 4 | | SM00057 | | S | | 275 |
| 004 | 20 | PA | | | 3-0 | 33-24-13 | D03400 | | 3 | | SM00058 | | S | | 150-199 |
| 004 | 20 | PA | | | 2-0 | 33-24-13 | D03400 | | 3 | | SM00058 | | S | | 275 |
| 005 | 20 | PA | | | 6-0 | 33-24-13 | D03400 | | 5 | | GD01776 | A.. | 2 | | 150-199, 275 |
| 008 | 20 | PA | | | 4-0 | 33-24-13 | D03402 | | 4 | | SM00057 | | S | | 150-199 |
| 008 | 20 | PA | | | 4-0 | 33-24-13 | SM00057 | | | S | D03402 | | 4 | | 275 |
| 009 | 20 | PA | | | 4-0 | 33-24-13 | D03402 | | 3 | | SM00058 | | S | | 150-199 |
| 009 | 20 | PA | | | 4-0 | 33-24-13 | SM00058 | | | S | D03402 | | 3 | | 275 |
| 010 | 20 | PA | | | 6-0 | 33-24-13 | GD01776 | | A.. | 2 | D03402 | | 5 | | 150-199 |
| 010 | 20 | PA | | | 6-0 | 33-24-13 | GD00723 | | A.. | 2 | D03402 | | 5 | | 275 |
| 011 | 20 | PA | | | 5-0 | 33-24-13 | SM00057 | | | S | D03404 | | 4 | | 275 |
| 012 | 20 | PA | | | 5-0 | 33-24-13 | SM00058 | | | S | D03404 | | 3 | | 275 |
| 013 | 20 | PA | | | 5-0 | 33-24-13 | GD00723 | | A.. | 2 | D03404 | | 5 | | 275 |
| 103 | 22 | PA | | | 3-0 | 33-24-13 | D03400 | | 3 | | SM00002 | | S | | 050-099 |
| 103 | 20 | PA | | | 3-0 | 33-24-13 | D03400 | | 3 | | SM00002 | | S | | 276-299 |
| 104 | 22 | PA | | | 3-0 | 33-24-13 | D03400 | | 4 | | SM00001 | | S | | 050-099 |
| 104 | 20 | PA | | | 3-0 | 33-24-13 | D03400 | | 4 | | SM00001 | | S | | 276-299 |
| 105 | 20 | PA | | | 5-0 | 33-24-13 | D03400 | | 5 | | GD01776 | A.. | 2 | | 050-099, 276-299 |
| 113 | 22 | PA | | | 4-0 | 33-24-13 | D03402 | | 3 | | SM00002 | | S | | 050-099 |
| 113 | 20 | PA | | | 5-0 | 33-24-13 | D03402 | | 3 | | SM00002 | | S | | 276-299 |

WIRE LIST

D280T132

91-21-11

Section W1150

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|---|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1152 | 286T1152 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | | | |
| 114 | 22 | | PA | | 4-0 | 33-24-13 | D03402 | | 4 | | | | | SM00001 | | S | | 050-099 |
| 114 | 20 | | PA | | 5-0 | 33-24-13 | D03402 | | 4 | | | | | SM00001 | | S | | 276-299 |
| 115 | 20 | | PA | | 6-0 | 33-24-13 | D03402 | | 5 | | | | | GD00723 | A.. | 2 | | 050-099, 276-299 |
| 123 | 22 | | PA | | 7-0 | 33-24-13 | D03404 | | 3 | | | | | SM00002 | | S | | 050-099 |
| 123 | 20 | | PA | | 5-0 | 33-24-13 | D03404 | | 3 | | | | | SM00002 | | S | | 276-299 |
| 124 | 22 | | PA | | 7-0 | 33-24-13 | D03404 | | 4 | | | | | SM00001 | | S | | 050-099 |
| 124 | 20 | | PA | | 5-0 | 33-24-13 | D03404 | | 4 | | | | | SM00001 | | S | | 276-299 |
| 125 | 20 | | PA | | 7-0 | 33-24-13 | D03404 | | 5 | | | | | GD00723 | A.. | 2 | | 050-099 |
| 125 | 20 | | PA | | 5-0 | 33-24-13 | D03404 | | 5 | | | | | GD00723 | A.. | 2 | | 276-299 |
| 201B | 22 | | PB | IA | 3-0 | 23-31-16 | D05984J | | 3 | | | | | SM00102 | | S | | 050-099, 276-299 |
| 201B | 22 | | PB | A | 3-0 | 23-31-16 | D05984J | | 3 | | | | | SM00026 | | S | | 150-199 |
| 201B | 22 | | PB | A | 2-0 | 23-31-16 | D05984J | | 3 | | | | | SM00024 | | S | | 275 |
| 201R | 22 | | PB | IA | 0-0 | 23-31-16 | D05984J | | 4 | | | | | SM00101 | | S | | 050-099, 276-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-16 | D05984J | | 4 | | | | | SM00025 | | S | | 150-199 |
| 201R | 22 | | PB | A | 0-0 | 23-31-16 | D05984J | | 4 | | | | | SM00023 | | S | | 275 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-16 | SM00102 | | | S | | | | D03400 | | 2 | | 050-099 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-16 | D03400 | | 2 | | | | | SM00102 | | S | | 276-299 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-16 | SM00101 | | | S | | | | D03400 | | 1 | | 050-099 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-16 | D03400 | | 1 | | | | | SM00101 | | S | | 276-299 |
| 203B | 22 | | PB | IC | 5-0 | 23-31-16 | SM00102 | | | S | | | | SM00104 | | S | | 050-099 |
| 203R | 22 | | PB | IC | 0-0 | 23-31-16 | SM00101 | | | S | | | | SM00103 | | S | | 050-099 |
| 204B | 22 | | PB | ID | 4-0 | 23-31-16 | D03402 | | 2 | | | | | SM00102 | | S | | 050-099 |
| 204B | 22 | | PB | ID | 5-0 | 23-31-16 | D03402 | | 2 | | | | | SM00102 | | S | | 276-299 |
| 204R | 22 | | PB | ID | 0-0 | 23-31-16 | D03402 | | 1 | | | | | SM00101 | | S | | 050-099, 276-299 |
| 206B | 22 | | PB | IF | 5-0 | 23-31-16 | D03404 | | 2 | | | | | SM00104 | | S | | 050-099 |
| 206B | 22 | | PB | IF | 5-0 | 23-31-16 | D03404 | | 2 | | | | | SM00102 | | S | | 276-299 |
| 206R | 22 | | PB | IF | 0-0 | 23-31-16 | D03404 | | 1 | | | | | SM00103 | | S | | 050-099 |
| 206R | 22 | | PB | IF | 0-0 | 23-31-16 | D03404 | | 1 | | | | | SM00101 | | S | | 276-299 |
| 220B | 22 | | PB | JS | 15-0 | 23-31-16 | SM00026 | | | S | | | | SP01698 | | S | | 150-199 |
| 220R | 22 | | PB | JS | 0-0 | 23-31-16 | SM00025 | | | S | | | | SP01696 | | S | | 150-199 |
| 224B | 22 | | PB | B | 3-0 | 23-31-16 | D03400 | | 2 | | | | | SM00026 | | S | | 150-199 |
| 224B | 22 | | PB | B | 2-0 | 23-31-16 | D03400 | | 2 | | | | | SM00024 | | S | | 275 |
| 224R | 22 | | PB | B | 0-0 | 23-31-16 | D03400 | | 1 | | | | | SM00025 | | S | | 150-199 |
| 224R | 22 | | PB | B | 0-0 | 23-31-16 | D03400 | | 1 | | | | | SM00023 | | S | | 275 |
| 225B | 22 | | PB | C | 4-0 | 23-31-16 | D03402 | | 2 | | | | | SM00026 | | S | | 150-199 |
| 225B | 22 | | PB | C | 4-0 | 23-31-16 | D03402 | | 2 | | | | | SM00024 | | S | | 275 |
| 225R | 22 | | PB | C | 0-0 | 23-31-16 | D03402 | | 1 | | | | | SM00025 | | S | | 150-199 |
| 225R | 22 | | PB | C | 0-0 | 23-31-16 | D03402 | | 1 | | | | | SM00023 | | S | | 275 |
| 228B | 22 | | PB | E | 5-0 | 23-31-16 | D03404 | | 2 | | | | | SM00024 | | S | | 275 |

WIRE LIST

D280T132

91-21-11

Section W1150

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1152 | 286T1152 | | | CENTER PSU MOD (continued) | | | | | | | | | | | |
| 228R | 22 | PB | E | 0-0 | 23-31-16 | D03404 | | 1 | | | SM00023 | | S | | 275 |
| 231B | 22 | PB | AA | 3-0 | 23-31-16 | D05984J | | 5 | | | SM00124 | | S | | 150-199 |
| 231R | 22 | PB | AA | 0-0 | 23-31-16 | D05984J | | 6 | | | SM00123 | | S | | 150-199 |
| 234B | 22 | PB | AB | 3-0 | 23-31-16 | D03400 | | 7 | | | SM00124 | | S | | 150-199 |
| 234R | 22 | PB | AB | 0-0 | 23-31-16 | D03400 | | 6 | | | SM00123 | | S | | 150-199 |
| 236B | 22 | PB | AD | 4-0 | 23-31-16 | D03402 | | 7 | | | SM00124 | | S | | 150-199 |
| 236R | 22 | PB | AD | 0-0 | 23-31-16 | D03402 | | 6 | | | SM00123 | | S | | 150-199 |
| 251B | 22 | PB | KA | 3-0 | 23-31-16 | D05984J | | 5 | | | SM00202 | | S | | 050-099 |
| 251R | 22 | PB | KA | 0-0 | 23-31-16 | D05984J | | 6 | | | SM00201 | | S | | 050-099 |
| 252B | 22 | PB | KB | 3-0 | 23-31-16 | D03400 | | 7 | | | SM00202 | | S | | 050-099 |
| 252R | 22 | PB | KB | 0-0 | 23-31-16 | D03400 | | 6 | | | SM00201 | | S | | 050-099 |
| 254B | 22 | PB | KD | 4-0 | 23-31-16 | D03402 | | 7 | | | SM00202 | | S | | 050-099 |
| 254R | 22 | PB | KD | 0-0 | 23-31-16 | D03402 | | 6 | | | SM00201 | | S | | 050-099 |
| 256B | 22 | PB | KF | 7-0 | 23-31-16 | D03404 | | 7 | | | SM00202 | | S | | 050-099 |
| 256R | 22 | PB | KF | 0-0 | 23-31-16 | D03404 | | 6 | | | SM00201 | | S | | 050-099 |
| 646B | 22 | PB | IE | 12-0 | 23-31-16 | SM00104 | | | S | | SP01698 | | S | | 050-099 |
| 646R | 22 | PB | IE | 0-0 | 23-31-16 | SM00103 | | | S | | SP01696 | | S | | 050-099 |
| W1154 | 286T1154 | | | FLIGHT DECK CLOSET LIGHTS | | | | | | | | | | | |
| 001 | 22 | PA | | 4-0 | 33-22-21 | D06386J | | =1 | | | L00737 | =G | C | | 150-154 |
| 001 | 22 | PA | | 10-0 | 33-22-21 | D06386J | | =1 | | | L00737 | =G | C | * | 155-157 |
| 001 | 22 | PA | | 3-7 | 33-22-21 | D06386J | | =1 | | | L00737 | =G | C | * | 275-299 |
| 011 | 22 | PA | | 11-0 | 33-22-21 | D06388P | | =1 | | | S00646 | =1 | C | | 150-157 |
| 011 | 22 | PA | | 4-9 | 33-22-21 | D06388P | | =1 | | | S00646 | =1 | C | | 275-299 |
| 012 | 22 | PA | | 13-0 | 33-22-21 | S00646 | | =2 | C | | L00737 | =P | C | | 150-154 |
| 012 | 22 | PA | | 2-0 | 33-22-21 | S00646 | | =2 | C | | L00738 | =P | C | * | 155-157 |
| 012 | 22 | PA | | 5-4 | 33-22-21 | L00738 | | =P | C | * | S00646 | =2 | C | | 275-299 |
| 013 | 22 | PA | | 4-0 | 33-22-21 | L00738 | | =P | C | * | L00737 | =P | C | | 155-157 |
| 013 | 22 | PA | | 4-2 | 33-22-21 | L00738 | | =P | C | * | L00737 | =P | C | | 275-299 |
| 014 | 22 | PA | | 4-0 | 33-22-21 | L00738 | | =G | C | | L00737 | =G | C | * | 155-157 |
| 014 | 22 | PA | | 4-2 | 33-22-21 | L00738 | | =G | C | | L00737 | =G | C | * | 275-299 |
| W1156 | 286T1156 | | | WINDOW HEAT,RIGHT WINDOW #2 | | | | | | | | | | | |
| 100K | 20 | 8U | 1A | 4-0 | 30-41-11 | D05870P | | 1 | | | SM00001 | | 9 | | ALL |
| 101O | 20 | 8U | 1A | 0-0 | 30-41-11 | D05870P | | 2 | | | SM00002 | | 9 | | ALL |
| 102Y | 22 | 8U | 1B | 0-0 | 30-41-11 | D05870P | | 3 | | | SM00003 | | 9 | | ALL |
| 103G | 22 | 8U | 1B | 0-0 | 30-41-11 | D05870P | | 4 | | | SM00004 | | 9 | | ALL |
| 104R | 22 | 8U | 1C | 0-0 | 30-41-11 | D05870P | | 5 | | | SM00005 | | 9 | | ALL |
| 105N | 22 | 8U | 1C | 0-0 | 30-41-11 | D05870P | | 6 | | | SM00006 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1150

Page 7

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|---------|-------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1156 | 286T1156 | | | | WINDOW HEAT,RIGHT WINDOW #2 (continued) | | | | | | | | | | |
| A-A | | | | 0-0 | 30-41-11 | SM00001 | | | 9 | | D01906 | | C | | ALL |
| A-B | | | | 0-0 | 30-41-11 | SM00002 | | | 9 | | D01906 | | D | | ALL |
| B-A | | | | 0-0 | 30-41-11 | SM00003 | | | 9 | | D01902 | | A | | ALL |
| B-B | | | | 0-0 | 30-41-11 | SM00004 | | | 9 | | D01902 | | B | | ALL |
| C-A | | | | 0-0 | 30-41-11 | SM00005 | | | 9 | | D01904 | | A | | ALL |
| C-B | | | | 0-0 | 30-41-11 | SM00006 | | | 9 | | D01904 | | B | | ALL |
| W1158 | 286T1158 | | | | WINDOW HEAT,LEFT WINDOW #2 | | | | | | | | | | |
| A-A | | | | 0-0 | 30-41-12 | D05872J | | | 1 | | D01920 | | C | | ALL |
| A-B | | | | 0-0 | 30-41-12 | D05872J | | | 2 | | D01920 | | D | | ALL |
| B-A | | | | 0-0 | 30-41-12 | D05872J | | | 3 | | D01916 | | A | | ALL |
| B-B | | | | 0-0 | 30-41-12 | D05872J | | | 4 | | D01916 | | B | | ALL |
| C-A | | | | 0-0 | 30-41-12 | D05872J | | | 5 | | D01918 | | A | | ALL |
| C-B | | | | 0-0 | 30-41-12 | D05872J | | | 6 | | D01918 | | B | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1160 | 286T1160 | | | CENTER,MID OXYGEN LATCHES STA 372-STA 488 | | | | | | | | | | | |
| 001 | 16 | | PA | | 3-0 | 35-21-14 | D05990J | | 1 | | SM00001 | | S | | 050-099 |
| 001 | 20 | | PA | | 5-0 | 35-21-14 | D00202 | | 1 | | SM00005 | | S | | 150-199 |
| 001 | 20 | | PA | | 0-18 | 35-21-14 | D00202 | | 1 | | SM00005 | | S | | 275 |
| 001 | 14 | | PA | | 3-0 | 35-21-14 | D05990J | | 1 | FN | SM00001 | | S | | 276-299 |
| 002 | 20 | | PA | | 4-0 | 35-21-14 | D00202 | | 2 | | GD00119 | | D.. | 2 | 150-199 |
| 002 | 20 | | PA | | 5-0 | 35-21-14 | D00202 | | 2 | | GD00119 | | D.. | 2 | 275 |
| 003 | 16 | | PA | | 6-0 | 35-21-14 | SM00001 | | | S | SM00003 | | S | | 050-099 |
| 003 | 14 | | PA | | 0-18 | 35-21-14 | D05990J | | 1 | FN | SM00005 | | S | | 150-199, 275 |
| 003 | 14 | | PA | | 6-0 | 35-21-14 | SM00001 | | | S | SM00003 | | S | | 276-299 |
| 004 | 14 | | PA | | 7-0 | 35-21-14 | SM00005 | | | S | SM00002 | | S | | 150-199 |
| 004 | 14 | | PA | | 6-0 | 35-21-14 | SM00005 | | | S | SM00002 | | S | | 275 |
| 005 | 16 | | PA | | 5-0 | 35-21-14 | SM00003 | | | S | SM00005 | | S | | 050-099 |
| 005 | 14 | | PA | | 5-0 | 35-21-14 | SM00003 | | | S | SM00005 | | S | | 276-299 |
| 006 | 20 | | PA | | 5-0 | 35-21-14 | SM00005 | | | S | D01192 | | 1 | | 150-199, 275 |
| 007 | 16 | | PA | | 5-0 | 35-21-14 | SM00005 | | | S | D05992P | | 1 | | 050-099 |
| 007 | 20 | | PA | | 4-0 | 35-21-14 | D01192 | | 2 | | GD01916 | | D.. | 2 | 150-199 |
| 007 | 20 | | PA | | 6-0 | 35-21-14 | D01192 | | 2 | | GD01916 | | D.. | 2 | 275 |
| 007 | 14 | | PA | | 5-0 | 35-21-14 | SM00005 | | | S | D05992P | | 1 | FO | 276-299 |
| 008 | 14 | | PA | | 6-0 | 35-21-14 | SM00002 | | | S | SM00004 | | S | | 150-199 |
| 008 | 14 | | PA | | 5-0 | 35-21-14 | SM00002 | | | S | SM00004 | | S | | 275 |
| 009 | 20 | | PA | | 3-0 | 35-21-14 | SM00002 | | | S | D01194 | | 1 | | 150-199, 275 |
| 010 | 20 | | PA | | 6-0 | 35-21-14 | D01194 | | 2 | | GD01916 | | D.. | 2 | 150-199, 275 |
| 012 | 20 | | PA | | 5-0 | 35-21-14 | SM00002 | | | S | D01196 | | 1 | | 150-199 |
| 012 | 20 | | PA | | 4-0 | 35-21-14 | SM00002 | | | S | D01196 | | 1 | | 275 |
| 013 | 20 | | PA | | 5-0 | 35-21-14 | D01196 | | 2 | | GD01918 | | D.. | 2 | 150-199, 275 |
| 014 | 14 | | PA | | 4-0 | 35-21-14 | SM00004 | | | S | D05992P | | 1 | FO | 150-199 |
| 014 | 14 | | PA | | 5-0 | 35-21-14 | SM00004 | | | S | D05992P | | 1 | FO | 275 |
| 015 | 20 | | PA | | 3-0 | 35-21-14 | SM00004 | | | S | D01198 | | 1 | | 150-199, 275 |
| 016 | 20 | | PA | | 5-0 | 35-21-14 | D01198 | | 2 | | GD01920 | | D.. | 2 | 150-199 |
| 016 | 20 | | PA | | 6-0 | 35-21-14 | D01198 | | 2 | | GD01920 | | D.. | 2 | 275 |
| 101 | 20 | | PA | | 3-0 | 35-21-14 | D00202 | | 1 | | SM00001 | | S | | 050-099, 276-299 |
| 102 | 20 | | PA | | 5-0 | 35-21-14 | D00202 | | 2 | | GD00119 | | D.. | 2 | 050-099, 276-299 |
| 111 | 20 | | PA | | 4-0 | 35-21-14 | D01192 | | 1 | | SM00001 | | S | | 050-099, 276-299 |
| 112 | 20 | | PA | | 6-0 | 35-21-14 | D01192 | | 2 | | GD01916 | | D.. | 2 | 050-099, 276-299 |
| 121 | 20 | | PA | | 3-0 | 35-21-14 | D01194 | | 1 | | SM00003 | | S | | 050-099, 276-299 |
| 122 | 20 | | PA | | 6-0 | 35-21-14 | D01194 | | 2 | | GD01916 | | D.. | 2 | 050-099, 276-299 |
| 131 | 20 | | PA | | 4-0 | 35-21-14 | D01196 | | 1 | | SM00003 | | S | | 050-099, 276-299 |
| 132 | 20 | | PA | | 4-0 | 35-21-14 | D01196 | | 2 | | GD01918 | | D.. | 2 | 050-099, 276-299 |
| 141 | 20 | | PA | | 3-0 | 35-21-14 | D01198 | | 1 | | SM00005 | | S | | 050-099, 276-299 |

WIRE LIST

D280T132

91-21-11

Section W1160

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|----------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1160 | 286T1160 | CENTER,MID OXYGEN LATCHES STA 372-STA 488 (continued) | | | | | | | | | | | | | | |
| 142 | 20 | PA | 6-0 | 35-21-14 | D01198 | | 2 | | | GD01920 | D.. | 2 | | 050-099, 276-299 | | |
| W1162 | 286T1162 | CENTER MID OXYGEN LATCHES STA 504-STA 591 | | | | | | | | | | | | | | |
| 001 | 16 | PA | 3-0 | 35-21-14 | D05992J | | 1 | | | SM00001 | | | S | 050-099 | | |
| 001 | 14 | PA | 2-0 | 35-21-14 | D05992J | | 1 | FN | | SM00001 | | | S | 150-199 | | |
| 001 | 14 | PA | 3-0 | 35-21-14 | D05992J | | 1 | FN | | SM00001 | | | S | 275-299 | | |
| 002 | 14 | PA | 5-0 | 35-21-14 | SM00001 | | | S | | SM00003 | | | S | 150-199 | | |
| 002 | 14 | PA | 6-0 | 35-21-14 | SM00001 | | | S | | SM00003 | | | S | 275 | | |
| 003 | 16 | PA | 6-0 | 35-21-14 | SM00001 | | | S | | SM00003 | | | S | 050-099 | | |
| 003 | 20 | PA | 2-0 | 35-21-14 | SM00001 | | | S | | D01200 | | 1 | | 150-199 | | |
| 003 | 20 | PA | 3-0 | 35-21-14 | SM00001 | | | S | | D01200 | | 1 | | 275 | | |
| 003 | 14 | PA | 6-0 | 35-21-14 | SM00001 | | | S | | SM00003 | | | S | 276-299 | | |
| 004 | 20 | PA | 8-0 | 35-21-14 | D01200 | | 2 | | | GD01924 | D.. | 2 | | 150-199, 275 | | |
| 005 | 16 | PA | 5-0 | 35-21-14 | SM00003 | | | S | | SM00005 | | | S | 050-099 | | |
| 005 | 14 | PA | 5-0 | 35-21-14 | SM00003 | | | S | | SM00005 | | | S | 276-299 | | |
| 006 | 20 | PA | 3-0 | 35-21-14 | SM00001 | | | S | | D01202 | | 1 | | 150-199 | | |
| 006 | 20 | PA | 4-0 | 35-21-14 | SM00001 | | | S | | D01202 | | 1 | | 275 | | |
| 007 | 16 | PA | 5-0 | 35-21-14 | SM00005 | | | S | | D05994P | | 1 | | 050-099 | | |
| 007 | 20 | PA | 5-0 | 35-21-14 | D01202 | | 2 | | | GD01924 | D.. | 2 | | 150-199 | | |
| 007 | 20 | PA | 6-0 | 35-21-14 | D01202 | | 2 | | | GD01924 | D.. | 2 | | 275 | | |
| 007 | 14 | PA | 5-0 | 35-21-14 | SM00005 | | | S | | D05994P | | 1 | FO | 276-299 | | |
| 008 | 20 | PA | 2-0 | 35-21-14 | SM00003 | | | S | | D01204 | | 1 | | 150-199 | | |
| 008 | 20 | PA | 3-0 | 35-21-14 | SM00003 | | | S | | D01204 | | 1 | | 275 | | |
| 009 | 20 | PA | 5-0 | 35-21-14 | D01204 | | 2 | | | GD01924 | D.. | 2 | | 150-199 | | |
| 009 | 20 | PA | 6-0 | 35-21-14 | D01204 | | 2 | | | GD01924 | D.. | 2 | | 275 | | |
| 010 | 14 | PA | 8-0 | 35-21-14 | SM00003 | | | S | | SM00005 | | | S | 150-199 | | |
| 010 | 14 | PA | 5-0 | 35-21-14 | SM00003 | | | S | | SM00005 | | | S | 275 | | |
| 011 | 20 | PA | 4-0 | 35-21-14 | SM00003 | | | S | | D01206 | | 1 | | 150-199, 275 | | |
| 012 | 20 | PA | 8-0 | 35-21-14 | D01206 | | 2 | | | GD01930 | D.. | 2 | | 150-199, 275 | | |
| 014 | 14 | PA | 3-0 | 35-21-14 | D05994P | | 1 | FO | | SM00005 | | | S | 150-199 | | |
| 014 | 14 | PA | 5-0 | 35-21-14 | D05994P | | 1 | FO | | SM00005 | | | S | 275 | | |
| 015 | 20 | PA | 2-0 | 35-21-14 | SM00005 | | | S | | D01208 | | 1 | | 150-199 | | |
| 015 | 20 | PA | 3-0 | 35-21-14 | SM00005 | | | S | | D01208 | | 1 | | 275 | | |
| 016 | 20 | PA | 6-0 | 35-21-14 | D01208 | | 2 | | | GD01930 | D.. | 2 | | 150-199, 275 | | |
| 101 | 20 | PA | 3-0 | 35-21-14 | D01200 | | 1 | | | SM00001 | | | S | 050-099, 276-299 | | |
| 102 | 20 | PA | 7-0 | 35-21-14 | D01200 | | 2 | | | GD01924 | D.. | 2 | | 050-099, 276-299 | | |
| 111 | 20 | PA | 4-0 | 35-21-14 | D01202 | | 1 | | | SM00001 | | | S | 050-099, 276-299 | | |
| 112 | 20 | PA | 6-0 | 35-21-14 | D01202 | | 2 | | | GD01924 | D.. | 2 | | 050-099, 276-299 | | |
| 121 | 20 | PA | 3-0 | 35-21-14 | D01204 | | 1 | | | SM00003 | | | S | 050-099, 276-299 | | |

WIRE LIST

D280T132

91-21-11

Section W1160

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|--------|---------|--------|-------------|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1162 | 286T1162 | | | CENTER MID OXYGEN LATCHES STA 504-STA 591 (continued) | | | | | | | | | | | | | |
| 122 | 20 | | PA | 6-0 | 35-21-14 | D01204 | | 2 | | | | | GD01924 | D.. | 2 | | 050-099, 276-299 |
| 131 | 20 | | PA | 4-0 | 35-21-14 | D01206 | | 1 | | | | | SM00003 | | S | | 050-099, 276-299 |
| 132 | 20 | | PA | 8-0 | 35-21-14 | D01206 | | 2 | | | | | GD01930 | D.. | 2 | | 050-099, 276-299 |
| 141 | 20 | | PA | 3-0 | 35-21-14 | D01208 | | 1 | | | | | SM00005 | | S | | 050-099, 276-299 |
| 142 | 20 | | PA | 6-0 | 35-21-14 | D01208 | | 2 | | | | | GD01930 | D.. | 2 | | 050-099, 276-299 |
| W1164 | 286T1164 | | | CENTER MID OXYGEN LATCHES STA 636-STA 654+098 | | | | | | | | | | | | | |
| 001 | 14 | | PA | 3-0 | 35-21-14 | D05994J | | 1 | FN | | | | SM00001 | | S | | 276-299 |
| 003 | 14 | | PA | 6-0 | 35-21-14 | SM00001 | | | S | | | | SM00003 | | S | | 276-299 |
| 004 | 14 | | PA | 2-0 | 35-21-14 | D05994J | | 1 | FN | | | | SM00002 | | S | | 275 |
| 005 | 20 | | PA | 2-0 | 35-21-14 | SM00002 | | | S | | | D01210 | | 1 | | | 275 |
| 005 | 14 | | PA | 5-0 | 35-21-14 | SM00003 | | | S | | | | SM00005 | | S | | 276-299 |
| 006 | 20 | | PA | 8-0 | 35-21-14 | D01210 | | 2 | | | | | GD05080 | D.. | 2 | | 275 |
| 007 | 14 | | PA | 6-0 | 35-21-14 | SM00002 | | | S | | | | SM00005 | | S | | 275 |
| 007 | 14 | | PA | 5-0 | 35-21-14 | SM00005 | | | S | | | | D05996P | | 1 | FO | 276-299 |
| 008 | 20 | | PA | 3-0 | 35-21-14 | SM00002 | | | S | | | | D00978 | | 1 | | 275 |
| 009 | 20 | | PA | 5-0 | 35-21-14 | D00978 | | 2 | | | | | GD05080 | D.. | 2 | | 275 |
| 011 | 20 | | PA | 2-0 | 35-21-14 | SM00005 | | | S | | | | D00980 | | 1 | | 275 |
| 012 | 20 | | PA | 5-0 | 35-21-14 | D00980 | | 2 | | | | | GD05080 | D.. | 2 | | 275 |
| 014 | 20 | | PA | 3-0 | 35-21-14 | SM00005 | | | S | | | | D01854 | | 1 | | 275 |
| 015 | 20 | | PA | 4-0 | 35-21-14 | D01854 | | 2 | | | | | GD04874 | D.. | 2 | | 275 |
| 016 | 14 | | PA | 4-0 | 35-21-14 | SM00005 | | | S | | | | SM00006 | | S | | 275 |
| 017 | 20 | | PA | 3-0 | 35-21-14 | SM00006 | | | S | | | | D01856 | | 1 | | 275 |
| 018 | 20 | | PA | 5-0 | 35-21-14 | D01856 | | 2 | | | | | GD04876 | D.. | 2 | | 275 |
| 019 | 14 | | PA | 5-0 | 35-21-14 | SM00006 | | | S | | | | D05996P | | 1 | FO | 275 |
| 101 | 20 | | PA | 3-0 | 35-21-14 | D01210 | | 1 | | | | | SM00001 | | S | | 276-299 |
| 102 | 20 | | PA | 7-0 | 35-21-14 | D01210 | | 2 | | | | | GD05080 | D.. | 2 | | 276-299 |
| 111 | 20 | | PA | 4-0 | 35-21-14 | D00978 | | 1 | | | | | SM00001 | | S | | 276-299 |
| 112 | 20 | | PA | 6-0 | 35-21-14 | D00978 | | 2 | | | | | GD05080 | D.. | 2 | | 276-299 |
| 121 | 20 | | PA | 3-0 | 35-21-14 | D00980 | | 1 | | | | | SM00003 | | S | | 276-299 |
| 122 | 20 | | PA | 6-0 | 35-21-14 | D00980 | | 2 | | | | | GD05080 | D.. | 2 | | 276-299 |
| 131 | 20 | | PA | 4-0 | 35-21-14 | D01854 | | 1 | | | | | SM00003 | | S | | 276-299 |
| 132 | 20 | | PA | 4-0 | 35-21-14 | D01854 | | 2 | | | | | GD04874 | D.. | 2 | | 276-299 |
| 141 | 20 | | PA | 3-0 | 35-21-14 | D01856 | | 1 | | | | | SM00005 | | S | | 276-299 |
| 142 | 20 | | PA | 6-0 | 35-21-14 | D01856 | | 2 | | | | | GD04876 | D.. | 2 | | 276-299 |
| W1166 | 286T1166 | | | CENTER MID OXYGEN LATCHES STA 922-STA 1009 | | | | | | | | | | | | | |
| 001 | 16 | | PA | 3-0 | 35-21-14 | SM00001 | | | S | | | | D05998J | | 1 | | 050-099 |
| 003 | 16 | | PA | 6-0 | 35-21-14 | SM00001 | | | S | | | | SM00003 | | S | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W1160
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1166 | 286T1166 | | | CENTER MID OXYGEN LATCHES STA 922-STA 1009 (continued) | | | | | | | | | | | | | |
| 101 | 20 | | PA | 3-0 | 35-21-14 | D10040 | | | 1 | | | | SM00001 | | S | | 050-099 |
| 102 | 20 | | PA | 5-0 | 35-21-14 | D10040 | | | 2 | | | | GD01944 | D.. | 2 | | 050-099 |
| 111 | 20 | | PA | 4-0 | 35-21-14 | D00986 | | | 1 | | | | SM00001 | | S | | 050-099 |
| 112 | 20 | | PA | 7-0 | 35-21-14 | D00986 | | | 2 | | | | GD01944 | D.. | 2 | | 050-099 |
| 121 | 20 | | PA | 3-0 | 35-21-14 | D10042 | | | 1 | | | | SM00003 | | S | | 050-099 |
| 122 | 20 | | PA | 7-0 | 35-21-14 | D10042 | | | 2 | | | | GD01952 | D.. | 2 | | 050-099 |
| 131 | 20 | | PA | 4-0 | 35-21-14 | D10044 | | | 1 | | | | SM00003 | | S | | 050-099 |
| 132 | 20 | | PA | 4-0 | 35-21-14 | D10044 | | | 2 | | | | GD01952 | D.. | 2 | | 050-099 |
| 141 | 20 | | PA | 6-0 | 35-21-14 | D10046 | | | 1 | | | | SM00003 | | S | | 050-099 |
| 142 | 20 | | PA | 7-0 | 35-21-14 | D10046 | | | 2 | | | | GD01952 | D.. | 2 | | 050-099 |
| W1168 | 286T1168 | | | CENTER AFT OXYGEN LATCHES STA 1025-STA 1141 | | | | | | | | | | | | | |
| 001 | 16 | | PA | 3-0 | 35-21-14 | D06000J | | | 1 | | | | SM00001 | | S | | 050-099 |
| 001 | 14 | | PA | 3-0 | 35-21-14 | D06000J | | | 1 | FN | | | SM00001 | | S | | 150-199, 275-299 |
| 002 | 14 | | PA | 7-0 | 35-21-14 | SM00001 | | | | S | | | SM00003 | | S | | 150-199 |
| 002 | 14 | | PA | 6-0 | 35-21-14 | SM00001 | | | | S | | | SM00003 | | S | | 275 |
| 003 | 16 | | PA | 6-0 | 35-21-14 | SM00001 | | | | S | | | SM00003 | | S | | 050-099 |
| 003 | 20 | | PA | 3-0 | 35-21-14 | SM00001 | | | | S | | | D01042 | 1 | | | 150-199, 275 |
| 003 | 14 | | PA | 6-0 | 35-21-14 | SM00001 | | | | S | | | SM00003 | | S | | 276-299 |
| 004 | 20 | | PA | 5-0 | 35-21-14 | D01042 | | | 2 | | | | GD01748 | D.. | 2 | | 150-199, 275 |
| 005 | 16 | | PA | 5-0 | 35-21-14 | SM00003 | | | | S | | | SM00005 | | S | | 050-099 |
| 005 | 14 | | PA | 5-0 | 35-21-14 | SM00003 | | | | S | | | SM00005 | | S | | 276-299 |
| 006 | 20 | | PA | 4-0 | 35-21-14 | SM00001 | | | | S | | | D02984 | 1 | | | 150-199, 275 |
| 007 | 16 | | PA | 5-0 | 35-21-14 | SM00005 | | | | S | | | D06002P | 1 | | | 050-099 |
| 007 | 20 | | PA | 7-0 | 35-21-14 | D02984 | | | 2 | | | | GD01748 | D.. | 2 | | 150-199, 275 |
| 007 | 14 | | PA | 5-0 | 35-21-14 | SM00005 | | | | S | | | D06002P | 1 | FO | | 276-299 |
| 008 | 14 | | PA | 5-0 | 35-21-14 | SM00003 | | | | S | | | SM00005 | | S | | 150-199, 275 |
| 009 | 20 | | PA | 3-0 | 35-21-14 | SM00003 | | | | S | | | D02986 | 1 | | | 150-199, 275 |
| 010 | 20 | | PA | 10-0 | 35-21-14 | D02986 | | | 2 | | | | GD01748 | D.. | 2 | | 150-199, 275 |
| 012 | 20 | | PA | 4-0 | 35-21-14 | SM00003 | | | | S | | | D02988 | 1 | | | 150-199, 275 |
| 013 | 20 | | PA | 4-0 | 35-21-14 | D02988 | | | 2 | | | | GD01750 | D.. | 2 | | 150-199 |
| 013 | 20 | | PA | 5-0 | 35-21-14 | D02988 | | | 2 | | | | GD01750 | D.. | 2 | | 275 |
| 014 | 14 | | PA | 4-0 | 35-21-14 | SM00005 | | | | S | | | D06002P | 1 | FO | | 150-199 |
| 014 | 14 | | PA | 5-0 | 35-21-14 | SM00005 | | | | S | | | D06002P | 1 | FO | | 275 |
| 015 | 20 | | PA | 3-0 | 35-21-14 | SM00005 | | | | S | | | D02990 | 1 | | | 150-199, 275 |
| 016 | 20 | | PA | 7-0 | 35-21-14 | D02990 | | | 2 | | | | GD01750 | D.. | 2 | | 150-199, 275 |
| 101 | 20 | | PA | 3-0 | 35-21-14 | D01042 | | | 1 | | | | SM00001 | | S | | 050-099, 276-299 |
| 102 | 20 | | PA | 5-0 | 35-21-14 | D01042 | | | 2 | | | | GD01748 | D.. | 2 | | 050-099, 276-299 |
| 111 | 20 | | PA | 4-0 | 35-21-14 | D02984 | | | 1 | | | | SM00001 | | S | | 050-099, 276-299 |

WIRE LIST

D280T132

91-21-11

Section W1160

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1168 | 286T1168 | | | CENTER AFT OXYGEN LATCHES STA 1025-STA 1141 (continued) | | | | | | | | | | | |
| 112 | 20 | | PA | | 7-0 | 35-21-14 | D02984 | | 2 | | GD01748 | D.. | 2 | | 050-099, 276-299 |
| 121 | 20 | | PA | | 3-0 | 35-21-14 | D02986 | | 1 | | SM00003 | | S | | 050-099, 276-299 |
| 122 | 20 | | PA | | 7-0 | 35-21-14 | D02986 | | 2 | | GD01750 | D.. | 2 | | 050-099, 276-299 |
| 131 | 20 | | PA | | 4-0 | 35-21-14 | D02988 | | 1 | | SM00003 | | S | | 050-099, 276-299 |
| 132 | 20 | | PA | | 5-0 | 35-21-14 | D02988 | | 2 | | GD01750 | D.. | 2 | | 050-099, 276-299 |
| 141 | 20 | | PA | | 3-0 | 35-21-14 | D02990 | | 1 | | SM00005 | | S | | 050-099, 276-299 |
| 142 | 20 | | PA | | 7-0 | 35-21-14 | D02990 | | 2 | | GD01750 | D.. | 2 | | 050-099, 276-299 |

WIRE LIST
D280T132

91-21-11
Section W1160
Page 5 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1170 | 286T1170 | | | CENTER AFT OXYGEN LATCHES STA 1157-STA 1273 | | | | | | | | | | | | | | |
| 001 | 16 | | PA | 3-0 | 35-21-14 | D06002J | | 1 | | | | | | SM00001 | | S | | 050-099 |
| 001 | 14 | | PA | 3-0 | 35-21-14 | D06002J | | 1 | FN | | | | | SM00001 | | S | | 150-199, 275-299 |
| 002 | 20 | | PA | 3-0 | 35-21-14 | SM00001 | | | S | | | | | D02992 | 1 | | | 150-199, 275 |
| 003 | 16 | | PA | 6-0 | 35-21-14 | SM00001 | | | S | | | | | SM00003 | | S | | 050-099 |
| 003 | 20 | | PA | 7-0 | 35-21-14 | D02992 | | 2 | | | | | | GD01756 | D.. | 2 | | 150-199 |
| 003 | 20 | | PA | 8-0 | 35-21-14 | D02992 | | 2 | | | | | | GD01756 | D.. | 2 | | 275 |
| 003 | 14 | | PA | 6-0 | 35-21-14 | SM00001 | | | S | | | | | SM00003 | | S | | 276-299 |
| 004 | 14 | | PA | 7-0 | 35-21-14 | SM00001 | | | S | | | | | SM00003 | | S | | 150-199 |
| 004 | 14 | | PA | 6-0 | 35-21-14 | SM00001 | | | S | | | | | SM00003 | | S | | 275 |
| 005 | 16 | | PA | 5-0 | 35-21-14 | SM00003 | | | S | | | | | SM00005 | | S | | 050-099 |
| 005 | 20 | | PA | 4-0 | 35-21-14 | SM00001 | | | S | | | | | D02994 | 1 | | | 150-199, 275 |
| 005 | 14 | | PA | 5-0 | 35-21-14 | SM00003 | | | S | | | | | SM00005 | | S | | 276-299 |
| 006 | 20 | | PA | 5-0 | 35-21-14 | D02994 | | 2 | | | | | | GD01756 | D.. | 2 | | 150-199 |
| 006 | 20 | | PA | 6-0 | 35-21-14 | D02994 | | 2 | | | | | | GD01756 | D.. | 2 | | 275 |
| 007 | 16 | | PA | 5-0 | 35-21-14 | SM00005 | | | S | | | | | D06004P | 1 | | | 050-099 |
| 007 | 14 | | PA | 5-0 | 35-21-14 | SM00005 | | | S | | | | | D08200P | 1 | FO | | 276-299 |
| 008 | 20 | | PA | 4-0 | 35-21-14 | SM00003 | | | S | | | | | D02996 | 1 | | | 150-199 |
| 008 | 20 | | PA | 3-0 | 35-21-14 | SM00003 | | | S | | | | | D02996 | 1 | | | 275 |
| 009 | 20 | | PA | 6-0 | 35-21-14 | D02996 | | 2 | | | | | | GD04906 | D.. | 2 | | 150-199 |
| 009 | 20 | | PA | 7-0 | 35-21-14 | D02996 | | 2 | | | | | | GD04906 | D.. | 2 | | 275 |
| 010 | 14 | | PA | 6-0 | 35-21-14 | SM00003 | | | S | | | | | SM00005 | | S | | 150-199 |
| 010 | 14 | | PA | 5-0 | 35-21-14 | SM00003 | | | S | | | | | SM00005 | | S | | 275 |
| 011 | 20 | | PA | 3-0 | 35-21-14 | SM00003 | | | S | | | | | D02998 | 1 | | | 150-199 |
| 011 | 20 | | PA | 4-0 | 35-21-14 | SM00003 | | | S | | | | | D02998 | 1 | | | 275 |
| 012 | 20 | | PA | 4-0 | 35-21-14 | D02998 | | 2 | | | | | | GD04906 | D.. | 2 | | 150-199 |
| 012 | 20 | | PA | 5-0 | 35-21-14 | D02998 | | 2 | | | | | | GD04906 | D.. | 2 | | 275 |
| 013 | 20 | | PA | 3-0 | 35-21-14 | SM00005 | | | S | | | | | D03000 | 1 | | | 150-199, 275 |
| 014 | 20 | | PA | 5-0 | 35-21-14 | D03000 | | 2 | | | | | | GD04908 | D.. | 2 | | 150-199 |
| 014 | 20 | | PA | 6-0 | 35-21-14 | D03000 | | 2 | | | | | | GD04908 | D.. | 2 | | 275 |
| 016 | 14 | | PA | 4-0 | 35-21-14 | SM00005 | | | S | | | | | D08200P | 1 | FO | | 150-199 |
| 016 | 14 | | PA | 5-0 | 35-21-14 | SM00005 | | | S | | | | | D08200P | 1 | FO | | 275 |
| 101 | 20 | | PA | 3-0 | 35-21-14 | D02992 | | 1 | | | | | | SM00001 | | S | | 050-099, 276-299 |
| 102 | 20 | | PA | 7-0 | 35-21-14 | D02992 | | 2 | | | | | | GD01756 | D.. | 2 | | 050-099, 276-299 |
| 111 | 20 | | PA | 4-0 | 35-21-14 | D02994 | | 1 | | | | | | SM00001 | | S | | 050-099, 276-299 |
| 112 | 20 | | PA | 6-0 | 35-21-14 | D02994 | | 2 | | | | | | GD01756 | D.. | 2 | | 050-099, 276-299 |
| 121 | 20 | | PA | 3-0 | 35-21-14 | D02996 | | 1 | | | | | | SM00003 | | S | | 050-099, 276-299 |
| 122 | 20 | | PA | 6-0 | 35-21-14 | D02996 | | 2 | | | | | | GD01756 | D.. | 2 | | 050-099, 276-299 |
| 131 | 20 | | PA | 4-0 | 35-21-14 | D02998 | | 1 | | | | | | SM00003 | | S | | 050-099, 276-299 |
| 132 | 20 | | PA | 5-0 | 35-21-14 | D02998 | | 2 | | | | | | GD01764 | D.. | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1170

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1170 | 286T1170 | | | CENTER AFT OXYGEN LATCHES STA 1157-STA 1273 (continued) | | | | | | | | | | | | | |
| 132 | 20 | | PA | | 5-0 | 35-21-14 | D02998 | | 2 | | | | GD04906 | D.. | 2 | | 276-299 |
| 141 | 20 | | PA | | 3-0 | 35-21-14 | D03000 | | 1 | | | | SM00005 | | S | | 050-099, 276-299 |
| 142 | 20 | | PA | | 7-0 | 35-21-14 | D03000 | | 2 | | | | GD01764 | D.. | 2 | | 050-099 |
| 142 | 20 | | PA | | 6-0 | 35-21-14 | D03000 | | 2 | | | | GD04908 | D.. | 2 | | 276-299 |
| W1171 | 286T1171 | | | TCAS COAX-E1-3 SHELF | | | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D06087P | | = C1 | | | | D02463A | | = C1 | | 050-099, 150-199, 277-299 |
| 01CX | | | | 78 A | 2-0 | 34-45-11 | D06087P | | = A1 | | | | D02463A | | 1 | | 050-099, 150-199, 277-299 |
| W1172 | 286T1172 | | | CENTER AFT OXYGEN LATCHES STA-1289-STA-1421 | | | | | | | | | | | | | |
| 001 | 16 | | PA | | 3-0 | 35-21-14 | D06004J | | 1 | | | | SM00001 | | S | | 050-099 |
| 001 | 14 | | PA | | 3-0 | 35-21-14 | D06004J | | 1 | FN | | | SM00002 | | S | | 150-199, 275 |
| 001 | 14 | | PA | | 3-0 | 35-21-14 | D06004J | | 1 | FN | | | SM00001 | | S | | 276-299 |
| 002 | 20 | | PA | | 3-0 | 35-21-14 | SM00002 | | | S | | | D03002 | | 1 | | 150-199, 275 |
| 003 | 16 | | PA | | 6-0 | 35-21-14 | SM00001 | | | S | | | SM00003 | | S | | 050-099 |
| 003 | 20 | | PA | | 7-0 | 35-21-14 | D03002 | | 2 | | | | GD04674 | D.. | 2 | | 150-199 |
| 003 | 20 | | PA | | 8-0 | 35-21-14 | D03002 | | 2 | | | | GD04674 | D.. | 2 | | 275 |
| 003 | 14 | | PA | | 6-0 | 35-21-14 | SM00001 | | | S | | | SM00003 | | S | | 276-299 |
| 005 | 16 | | PA | | 5-0 | 35-21-14 | SM00003 | | | S | | | SM00005 | | S | | 050-099 |
| 005 | 14 | | PA | | 3-0 | 35-21-14 | SM00002 | | | S | | | SM00003 | | S | | 150-199 |
| 005 | 14 | | PA | | 6-0 | 35-21-14 | SM00002 | | | S | | | SM00003 | | S | | 275 |
| 005 | 14 | | PA | | 5-0 | 35-21-14 | SM00003 | | | S | | | SM00005 | | S | | 276-299 |
| 006 | 20 | | PA | | 4-0 | 35-21-14 | SM00002 | | | S | | | D03004 | | 1 | | 150-199, 275 |
| 007 | 16 | | PA | | 5-0 | 35-21-14 | SM00005 | | | S | | | D06006P | | 1 | | 050-099 |
| 007 | 20 | | PA | | 5-0 | 35-21-14 | D03004 | | 2 | | | | GD04674 | D.. | 2 | | 150-199 |
| 007 | 20 | | PA | | 6-0 | 35-21-14 | D03004 | | 2 | | | | GD04674 | D.. | 2 | | 275 |
| 007 | 14 | | PA | | 5-0 | 35-21-14 | SM00005 | | | S | | | D06006P | | 1 | FO | 276-299 |
| 008 | 14 | | PA | | 8-0 | 35-21-14 | SM00003 | | | S | | | SM00005 | | S | | 150-199 |
| 008 | 14 | | PA | | 5-0 | 35-21-14 | SM00003 | | | S | | | SM00005 | | S | | 275 |
| 009 | 20 | | PA | | 5-0 | 35-21-14 | SM00003 | | | S | | | D03006 | | 1 | | 150-199 |
| 009 | 20 | | PA | | 3-0 | 35-21-14 | SM00003 | | | S | | | D03006 | | 1 | | 275 |
| 010 | 20 | | PA | | 6-0 | 35-21-14 | D03006 | | 2 | | | | GD04674 | D.. | 2 | | 150-199, 275 |
| 012 | 20 | | PA | | 7-0 | 35-21-14 | SM00003 | | | S | | | D03008 | | 1 | | 150-199 |
| 012 | 20 | | PA | | 4-0 | 35-21-14 | SM00003 | | | S | | | D03008 | | 1 | | 275 |
| 013 | 20 | | PA | | 4-0 | 35-21-14 | D03008 | | 2 | | | | GD01774 | D.. | 2 | | 150-199 |
| 013 | 20 | | PA | | 5-0 | 35-21-14 | D03008 | | 2 | | | | GD01774 | D.. | 2 | | 275 |
| 014 | 14 | | PA | | 4-0 | 35-21-14 | SM00005 | | | S | | | D06006P | | 1 | FO | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1170

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|--|----|-----|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1172 | 286T1172 | CENTER AFT OXYGEN LATCHES STA-1289-STA-1421 (continued) | | | | | | | | | | | | | | |
| 014 | 14 | PA | | 5-0 | 35-21-14 | SM00005 | | | | S | D06006P | 1 | FO | | 275 | |
| 015 | 20 | PA | | 3-0 | 35-21-14 | SM00005 | | | | S | D03010 | 1 | | | 150-199, 275 | |
| 016 | 20 | PA | | 6-0 | 35-21-14 | D03010 | | 2 | | | GD01774 | D.. | 2 | | 150-199 | |
| 016 | 20 | PA | | 7-0 | 35-21-14 | D03010 | | 2 | | | GD01774 | D.. | 2 | | 275 | |
| 101 | 20 | PA | | 3-0 | 35-21-14 | D03002 | | 1 | | | SM00001 | | | S | 050-099, 276-299 | |
| 102 | 20 | PA | | 7-0 | 35-21-14 | D03002 | | 2 | | | GD04674 | D.. | 2 | | 050-099, 276-299 | |
| 111 | 20 | PA | | 4-0 | 35-21-14 | D03004 | | 1 | | | SM00001 | | | S | 050-099, 276-299 | |
| 112 | 20 | PA | | 6-0 | 35-21-14 | D03004 | | 2 | | | GD04674 | D.. | 2 | | 050-099, 276-299 | |
| 121 | 20 | PA | | 3-0 | 35-21-14 | D03006 | | 1 | | | SM00003 | | | S | 050-099, 276-299 | |
| 122 | 20 | PA | | 6-0 | 35-21-14 | D03006 | | 2 | | | GD04674 | D.. | 2 | | 050-099, 276-299 | |
| 131 | 20 | PA | | 4-0 | 35-21-14 | D03008 | | 1 | | | SM00003 | | | S | 050-099, 276-299 | |
| 132 | 20 | PA | | 4-0 | 35-21-14 | D03008 | | 2 | | | GD01774 | D.. | 2 | | 050-099, 276-299 | |
| 141 | 20 | PA | | 3-0 | 35-21-14 | D03010 | | 1 | | | SM00005 | | | S | 050-099, 276-299 | |
| 142 | 20 | PA | | 7-0 | 35-21-14 | D03010 | | 2 | | | GD01774 | D.. | 2 | | 050-099, 276-299 | |
| W1174 | 286T1174 | CENTER AFT OXYGEN LATCHES STA 1421-STA 1479 | | | | | | | | | | | | | | |
| 001 | 16 | PA | | 4-0 | 35-21-14 | D06006J | | 1 | | | SM00001 | | | S | 050-099 | |
| 001 | 14 | PA | | 4-0 | 35-21-14 | D06006J | | 1 | FN | | SM00001 | | | S | 150-199, 275-299 | |
| 002 | 20 | PA | | 3-0 | 35-21-14 | SM00001 | | | | S | D03014 | 1 | | | 150-199, 275 | |
| 003 | 20 | PA | | 8-0 | 35-21-14 | D03014 | | 2 | | | GD01776 | D.. | 2 | | 150-199, 275 | |
| 004 | 20 | PA | | 5-0 | 35-21-14 | SM00001 | | | | S | D03832 | 1 | | | 275 | |
| 005 | 20 | PA | | 9-0 | 35-21-14 | D03832 | | 2 | | | GD01776 | D.. | 2 | | 275 | |
| 007 | 20 | PA | | 4-0 | 35-21-14 | SM00001 | | | | S | D03012 | 1 | | | 150-199, 275 | |
| 008 | 20 | PA | | 6-0 | 35-21-14 | D03012 | | 2 | | | GD01776 | D.. | 2 | | 150-199, 275 | |
| 101 | 20 | PA | | 4-0 | 35-21-14 | D03012 | | 1 | | | SM00001 | | | S | 050-099, 276-299 | |
| 102 | 20 | PA | | 6-0 | 35-21-14 | D03012 | | 2 | | | GD01776 | D.. | 2 | | 050-099, 276-299 | |
| 111 | 20 | PA | | 4-0 | 35-21-14 | D03014 | | 1 | | | SM00001 | | | S | 050-099 | |
| 111 | 20 | PA | | 3-0 | 35-21-14 | D03014 | | 1 | | | SM00001 | | | S | 276-299 | |
| 112 | 20 | PA | | 5-0 | 35-21-14 | D03014 | | 2 | | | GD00723 | D.. | 2 | | 050-099, 276-299 | |
| 121 | 20 | PA | | 7-0 | 35-21-14 | D03832 | | 1 | | | SM00001 | | | S | 050-099 | |
| 121 | 20 | PA | | 5-0 | 35-21-14 | D03832 | | 1 | | | SM00001 | | | S | 276-299 | |
| 122 | 20 | PA | | 8-0 | 35-21-14 | D03832 | | 2 | | | GD00723 | D.. | 2 | | 050-099 | |
| 122 | 20 | PA | | 6-0 | 35-21-14 | D03832 | | 2 | | | GD00723 | D.. | 2 | | 276-299 | |
| W1175 | 286T1175 | TCAS COAX-E1-3 SHELF | | | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 34-45-11 | D06089P | | =C1 | | | D02463A | | =C2 | | 050-099, 150-199, 277-299 | |
| 01CX | | 78 | A | 2-0 | 34-45-11 | D06089P | | =A1 | | | D02463A | | 2 | | 050-099, 150-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W1170

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1177 | 286T1177 | | | TCAS COAX-E1-3 SHELF | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D06091P | = | C1 | | D02463A | = | C3 | | 050-099, 150-199, 277-299 |
| 01CX | | 78 | | A | 2-0 | 34-45-11 | D06091P | = | A1 | | D02463A | | 3 | | 050-099, 150-199, 277-299 |
| W1178 | 286T1178 | | | L FWD COAT CLOSET LTG | | | | | | | | | | | |
| 001 | 22 | | | PA | 6-0 | 33-22-21 | D05720P | = | 1 | | S00042 | = | 1 | I | 050-099 |
| 002 | 22 | | | PA | 4-0 | 33-22-21 | L00024 | = | P | C | S00042 | = | 2 | I | 050-099 |
| 003 | 22 | | | PA | 5-0 | 33-22-21 | L00024 | = | G | C | D05722J | = | 1 | | 050-099 |
| W1179 | 286T1179 | | | TCAS COAX-E1-3 SHELF | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D06093P | = | C1 | | D02463A | = | C4 | | 050-099, 150-199, 277-299 |
| 01CX | | 78 | | A | 2-0 | 34-45-11 | D06093P | = | A1 | | D02463A | | 4 | | 050-099, 150-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W1170
Page 4 End
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|-----------------------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1181 | 286T1181 | | | | TCAS COAX-E1-3 SHELF | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D06095P | = | C1 | | D02463B | = | C1 | | 050-099, 150-199, 277-299 |
| 01CX | | 78 | | A | 2-0 | 34-45-11 | D06095P | = | A1 | | D02463B | | 1 | | 050-099, 150-199, 277-299 |
| 02CO | | | | B | 0-0 | 34-45-11 | D06133P | = | C1 | | D02463B | = | C2 | | 050-099, 150-199, 277-299 |
| 02CX | | 78 | | B | 2-0 | 34-45-11 | D06133P | = | A1 | | D02463B | | 2 | | 050-099, 150-199, 277-299 |
| 03CO | | | | C | 0-0 | 34-45-11 | D06135P | = | C1 | | D02463B | = | C3 | | 050-099, 150-199, 277-299 |
| 03CX | | 78 | | C | 2-0 | 34-45-11 | D06135P | = | A1 | | D02463B | | 3 | | 050-099, 150-199, 277-299 |
| 04CO | | | | D | 0-0 | 34-45-11 | D06137P | = | C1 | | D02463B | = | C4 | | 050-099, 150-199, 277-299 |
| 04CX | | 78 | | D | 2-0 | 34-45-11 | D06137P | = | A1 | | D02463B | | 4 | | 050-099, 150-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W1180
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|-------|------|--------|---------|-------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1191 | 286T1191 | | | SATCOM SYSTEM RF DISTRIBUTION,COAX | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-12 | D02647C | = C12 | | | D02649C | = C12 | | | 150, 153-199, 277-299 |
| 01CX | | 78 | | A | 2-6 | 23-25-12 | D02647C | 12 | | | D02649C | 12 | | | 150, 153-199, 277-299 |
| 02CO | | | | D | 0-0 | 23-25-12 | D02647C | = C13 | | | D02649C | = C13 | | | 150, 153-199 |
| 02CX | | 78 | | D | 2-6 | 23-25-12 | D02647C | 13 | | | D02649C | 13 | | | 150, 153-199 |
| W1192 | 286T1192 | | | FWD COMPARTMENT CTR COAT CLOSET | | | | | | | | | | | |
| 001 | 22 | | | PA | 7-0 | 33-22-21 | D08124P | = 1 | | | S00526 | = 1 | C | * | 050-099 |
| 002 | 22 | | | PA | 7-0 | 33-22-21 | L00411 | = P | C | | S00526 | = 2 | C | | 050-099 |
| 003 | 22 | | | PA | 6-0 | 33-22-21 | L00607 | = G | C | * | D08126J | = 1 | | | 050-099 |
| 004 | 22 | | | PA | 4-0 | 33-22-21 | L00411 | = G | C | | L00607 | = G | C | * | 050-099 |
| 007 | 22 | | | PA | 7-0 | 33-22-21 | S00526 | = 1 | C | * | S00540 | = 1 | C | | 050-099 |
| 008 | 22 | | | PA | 7-0 | 33-22-21 | L00607 | = P | C | | S00540 | = 2 | C | | 050-099 |
| W1193 | 286T1193 | | | SATCOM SYSTEM RF DISTRIBUTION,COAX | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-12 | D02647C | = C13 | | | D02649C | = C13 | | | 277-299 |
| 01CX | | 78 | | A | 2-6 | 23-25-12 | D02647C | 13 | | | D02649C | 13 | | | 277-299 |
| W1194 | 286T1194 | | | P23-LANDING & TAXI LT XFMR WIRING | | | | | | | | | | | |
| A-A | | | | | 0-0 | 33-42-11 | T00144 | BLK | | | TB5124 | 3 | N | | ALL |
| A-B | | | | | 0-0 | 33-42-11 | T00144 | GRA | | | TB5124 | 2 | N | | ALL |
| A-C | | | | | 0-0 | 33-42-11 | T00144 | GRY | | | T00144 | CAP | Y | | ALL |
| A-D | | | | | 0-0 | 33-42-11 | T00144 | GRO | | | TB5124 | 1 | N | | ALL |
| A-E | | | | | 0-0 | 33-42-11 | T00144 | GRR | | | T00144 | CAP | Y | | ALL |
| A-F | | | | | 0-0 | 33-42-11 | T00144 | BRN | | | TB5124 | 6 | N | | ALL |
| B-A | | | | | 0-0 | 33-42-11 | T00143 | BLK | | | TB5120 | 3 | N | | ALL |
| B-B | | | | | 0-0 | 33-42-11 | T00143 | GRA | | | TB5120 | 2 | N | | ALL |
| B-C | | | | | 0-0 | 33-42-11 | T00143 | GRY | | | T00143 | CAP | Y | | ALL |
| B-D | | | | | 0-0 | 33-42-11 | T00143 | GRO | | | TB5120 | 1 | N | | ALL |
| B-E | | | | | 0-0 | 33-42-11 | T00143 | GRR | | | T00143 | CAP | Y | | ALL |
| B-F | | | | | 0-0 | 33-42-11 | T00143 | BRN | | | TB5120 | 6 | N | | ALL |
| C-A | | | | | 0-0 | 33-42-21 | T00188 | BLK | | | TB5122 | 4 | N | | ALL |
| C-B | | | | | 0-0 | 33-42-21 | T00188 | GRA | | | TB5124 | 5 | N | | ALL |
| C-C | | | | | 0-0 | 33-42-21 | T00188 | GRY | | | T00188 | CAP | Y | | ALL |
| C-D | | | | | 0-0 | 33-42-21 | T00188 | GRO | | | TB5124 | 4 | N | | ALL |
| C-E | | | | | 0-0 | 33-42-21 | T00188 | GRR | | | T00188 | CAP | Y | | ALL |
| C-F | | | | | 0-0 | 33-42-21 | T00188 | BRN | | | TB5124 | 6 | N | | ALL |
| D-A | | | | | 0-0 | 33-42-21 | T00187 | BLK | | | TB5122 | 5 | N | | ALL |
| D-B | | | | | 0-0 | 33-42-21 | T00187 | GRA | | | TB5120 | 5 | N | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W1190
 Page 1
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1194 | 286T1194 | | | P23-LANDING & TAXI LT XFMR WIRING (continued) | | | | | | | | | | | | |
| D-C | | | | 0-0 | 33-42-21 | T00187 | | GRY | | | T00187 | | CAP | Y | ALL | |
| D-D | | | | 0-0 | 33-42-21 | T00187 | | GRO | | | TB5120 | 4 | N | | ALL | |
| D-E | | | | 0-0 | 33-42-21 | T00187 | | GRR | | | T00187 | | CAP | Y | ALL | |
| D-F | | | | 0-0 | 33-42-21 | T00187 | | BRN | | | TB5120 | 6 | N | | ALL | |
| W1195 | 286T1195 | | | COAX-SATCOM M1781 RF UNIT TO AC1102 (SPLITTER) | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-12 | D02649B | = | C71 | | | D06175P | = | C1 | | 150, 153-199, 277-299 | |
| 01CX | | 78 | A | 2-0 | 23-25-12 | D02649B | | 71 | | | D06175P | = | A1 | | 150, 153-199, 277-299 | |
| W1197 | 286T1197 | | | COAX-SATCOM,M1781 RF UNIT TO AC1102 (COMBINER) | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-12 | D02649A | = | C71 | | | D06177P | = | C1 | | 150, 153-199, 277-299 | |
| 01CX | | 78 | A | 2-6 | 23-25-12 | D02649A | | 71 | | | D06177P | = | A1 | | 150, 153-199, 277-299 | |
| W1198 | 286T1198 | | | LEFT FWD OXYGEN LATCHES STA 346 | | | | | | | | | | | | |
| 001 | 20 | | PA | 8-0 | 35-21-12 | D06136P | | 1 | | | D01880 | | 1 | | 275-299 | |
| 002 | 20 | | PA | 8-0 | 35-21-12 | D06136P | | 2 | | | D01880 | | 2 | | 275-299 | |
| 003 | 18 | | PA | 10-0 | 33-22-31 | D06136P | | 3 | DL | | D13702 | | 3 | DK | 275-299 | |
| 004 | 18 | | PA | 10-0 | 33-22-31 | D06136P | | 4 | DL | | D13702 | | 1 | DK | 275-299 | |
| 005 | 18 | | PA | 9-11 | 33-22-31 | D13702 | | 2 | DK | | SP03730 | | 9 | | 275-299 | |
| 006 | 18 | | PA | 4-6 | 33-22-31 | D06136P | | 5 | DL | | SP03728 | | 9 | | 275-299 | |
| 007 | 20 | | PA | 4-0 | 33-24-12 | D06136P | | 6 | | | L01175 | FSB | C | | 275-276, 280-299 | |
| 007 | 20 | | PA | 4-0 | 33-24-12 | D06136P | | 6 | | | L01175 | | 3 | C | 277-278 | |
| 008 | 20 | | PA | 4-0 | 33-24-12 | D06136P | | 7 | | | L01175 | NS | C | | 275-276, 280-299 | |
| 008 | 20 | | PA | 4-0 | 33-24-12 | D06136P | | 7 | | | L01175 | | 1 | C | 277-278 | |
| 009 | 20 | | PA | 4-0 | 33-24-12 | D06136P | | 8 | | | L01175 | GND | C | | 275-276, 280-299 | |
| 009 | 20 | | PA | 4-0 | 33-24-12 | D06136P | | 8 | | | L01175 | | 2 | C | 277-278 | |
| A-A | | | | 0-0 | 33-22-31 | L00647 | = | P | | | SP03730 | | 9 | | 275-299 | |
| A-B | | | | 0-0 | 33-22-31 | L00647 | = | G | | | SP03728 | | 9 | | 275-299 | |
| W1199 | 286T1199 | | | COAX-SATCOM,M1782 HPA TO AP1001 (SPLITTER) | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-12 | D02651A | = | C71 | | | D06187J | = | C1 | | 156-157, 166-199, 277-299 | |
| 01CX | | 78 | A | 1-2 | 23-25-12 | D02651A | | 71 | | | D06187J | = | A1 | | 156-157, 166-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W1190

Page 2 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|--|----|-----|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1201 | 286T1201 | DLEC SPOILER CONT PCA 2,W/W DISC TO WING DISC | | | | | | | | | | | | | | | |
| 001 | 20 | | UA | | 1-0 | 27-61-14 | SM00001 | | | | W | | D05461J | 2 | | | ALL |
| 002 | 20 | | UA | | 1-0 | 27-61-14 | SM00002 | | | | W | | D05461J | 4 | | | ALL |
| 003 | 20 | | UA | | 1-0 | 27-61-14 | SM00001 | | | | W | | D05461J | 1 | | | ALL |
| 004 | 20 | | UA | | 1-0 | 27-61-14 | SM00002 | | | | W | | D05461J | 3 | | | ALL |
| 005 | 18 | | UA | | 2-0 | 27-61-14 | GD00443 | | | S.. | N | | D05461J | 10 | | | ALL |
| WBK | 20 | | 7N | 1B | 47-0 | 27-61-14 | D05215J | | | 2 | | | D05461J | 8 | | | ALL |
| WBKZ | | | | 1B | 0-0 | 27-61-14 | GD00419 | | | S.. | N | | GD00443 | S.. | N | | ALL |
| WBN | 20 | | 7N | 1B | 0-0 | 27-61-14 | D05215J | | | 6 | | | D05461J | 6 | | | ALL |
| WBU | 20 | | 7N | 1B | 0-0 | 27-61-14 | D05215J | | | 3 | | | SM00002 | | W | | ALL |
| WOR | 20 | | 7N | 1B | 0-0 | 27-61-14 | D05215J | | | 5 | | | D05461J | 5 | | | ALL |
| WRB | 20 | | 7N | 1B | 0-0 | 27-61-14 | D05215J | | | 7 | | | D05461J | 7 | | | ALL |
| WRD | 20 | | 7N | 1B | 0-0 | 27-61-14 | D05215J | | | 1 | | | SM00001 | | W | | ALL |
| WVI | 20 | | 7N | 1B | 0-0 | 27-61-14 | D05215J | | | 4 | | | D05461J | 9 | | | ALL |
| W1203 | 286T1203 | ELEC SPOILER CONT PCA 3,W/W DISC TO WING DISC | | | | | | | | | | | | | | | |
| 001 | 20 | | UA | | 1-0 | 27-61-15 | SM00001 | | | | W | | D05463J | 2 | | | ALL |
| 002 | 20 | | UA | | 1-0 | 27-61-15 | SM00002 | | | | W | | D05463J | 4 | | | ALL |
| 003 | 20 | | UA | | 1-0 | 27-61-15 | SM00001 | | | | W | | D05463J | 1 | | | ALL |
| 004 | 20 | | UA | | 1-0 | 27-61-15 | SM00002 | | | | W | | D05463J | 3 | | | ALL |
| 005 | 18 | | UA | | 1-4 | 27-61-15 | GD00441 | | | S.. | N | | D05463J | 10 | | | ALL |
| WBK | 20 | | 7N | 1B | 48-11 | 27-61-15 | D05213J | | | 2 | | | D05463J | 8 | | | ALL |
| WBKZ | | | | 1B | 0-0 | 27-61-15 | GD00417 | | | S.. | N | | GD00441 | S.. | N | | ALL |
| WBN | 20 | | 7N | 1B | 0-0 | 27-61-15 | D05213J | | | 6 | | | D05463J | 6 | | | ALL |
| WBU | 20 | | 7N | 1B | 0-0 | 27-61-15 | D05213J | | | 3 | | | SM00002 | | W | | ALL |
| WOR | 20 | | 7N | 1B | 0-0 | 27-61-15 | D05213J | | | 5 | | | D05463J | 5 | | | ALL |
| WRB | 20 | | 7N | 1B | 0-0 | 27-61-15 | D05213J | | | 7 | | | D05463J | 7 | | | ALL |
| WRD | 20 | | 7N | 1B | 0-0 | 27-61-15 | D05213J | | | 1 | | | SM00001 | | W | | ALL |
| WVI | 20 | | 7N | 1B | 0-0 | 27-61-15 | D05213J | | | 4 | | | D05463J | 9 | | | ALL |
| W1204 | 286T1204 | PANEL AREA FEEDER | | | | | | | | | | | | | | | |
| 001 | 22 | | PA | | 30-0 | 32-31-11 | D04870P | | | 1 | | | D05348P | 1 | | | ALL |
| 002 | 18 | | PA | | 30-0 | 28-41-12 | D04870P | | | 2 | DL | | D05348P | 2 | DK | | ALL |
| 004 | 22 | | PA | | 16-0 | 29-11-31 | D04870P | | | 7 | | | D05352P | 51 | | | ALL |
| 006 | 24 | | PK | | 16-0 | 36-11-21 | D04870P | | | 15 | | | D05352P | 41 | | | ALL |
| 007 | 24 | | PK | | 16-0 | 36-11-21 | D04870P | | | 16 | | | D05352P | 42 | | | ALL |
| 008 | 24 | | PK | | 16-0 | 36-11-21 | D04870P | | | 18 | | | D05352P | 43 | | | ALL |
| 009 | 24 | | PK | | 30-0 | 21-53-12 | D04870P | | | 6 | | | D05348P | 18 | | | ALL |
| 010 | 24 | | PK | | 17-0 | 21-53-12 | D05352P | | | 4 | | | D05348P | 19 | | | ALL |
| 011 | 24 | | PK | | 17-0 | 21-53-12 | D05352P | | | 5 | | | D05348P | 11 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1200

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1204 | 286T1204 | | | PANEL AREA FEEDER (continued) | | | | | | | | | | | | |
| 012 | 24 | | PK | | 17-0 | 21-53-12 | D05352P | | 6 | | | | D05348P | 12 | | ALL |
| 013 | 24 | | PK | | 17-0 | 21-53-12 | D05352P | | 7 | | | | D05348P | 13 | | ALL |
| 014 | 24 | | PK | | 17-0 | 21-53-12 | D05352P | | 8 | | | | D05348P | 14 | | ALL |
| 015 | 24 | | PK | | 17-0 | 21-53-12 | D05352P | | 9 | | | | D05348P | 15 | | ALL |
| 016 | 24 | | PK | | 17-0 | 21-53-12 | D05352P | | 10 | | | | D05348P | 16 | | ALL |
| 017 | 22 | | PA | | 16-0 | 36-11-21 | D04870P | | 20 | | | | D05352P | 44 | | ALL |
| 018 | 18 | | PA | | 11-0 | 33-31-21 | D05348P | | 21 | DK | | | D05346P | 4 | | ALL |
| 019 | 24 | | PK | | 30-0 | 21-58-16 | D04870P | | 8 | | | | D05348P | 5 | | ALL |
| 020 | 24 | | PK | | 30-0 | 21-58-16 | D04870P | | 9 | | | | D05348P | 6 | | ALL |
| 021 | 24 | | PK | | 30-0 | SPARE | D04870P | | 10 | | | | D05348P | 20 | | 050-099, 150-156, 162-166, 275-276 |
| 021 | 18 | | PQ | AU | 30-0 | SPARE | D04870P | | 10 | DL | | | D05348P | 20 | DK | 157, 167-199, 277-299 |
| 021Z | | | | AU | 0-0 | SPARE | D04870P | | | DED | | | D05348P | DED | | 157, 167-199, 277-299 |
| 022 | 24 | | PK | | 10-0 | 21-26-11 | D05346P | | 1 | | | | D05352P | 11 | | ALL |
| 024 | 24 | | PK | | 16-0 | 36-11-41 | D04870P | | 12 | | | | D05352P | 12 | | ALL |
| 025 | 24 | | PK | | 16-0 | 36-11-41 | D04870P | | 13 | | | | D05352P | 13 | | ALL |
| 026 | 24 | | PK | | 16-0 | 36-11-41 | D04870P | | 14 | | | | D05352P | 14 | | ALL |
| 027 | 22 | | PA | | 16-0 | 36-11-21 | D04870P | | 26 | | | | D05352P | 45 | | ALL |
| 028 | 24 | | PK | | 30-0 | 21-58-16 | D04870P | | 5 | | | | D05348P | 17 | | ALL |
| 029 | 24 | | PK | | 16-0 | 29-33-11 | D04870P | | 29 | | | | D05352P | 46 | | ALL |
| 030 | 22 | | PA | | 11-0 | 52-11-12 | D05346P | | 2 | | | | D05348P | 27 | | 050-099, 150-199 |
| 030 | 20 | | PA | | 11-0 | 52-11-12 | D05346P | | 2 | | | | D05348P | 27 | | 275-299 |
| 031 | 22 | | PA | | 16-0 | 29-33-11 | D04870P | | 30 | | | | D05352P | 47 | | ALL |
| 032 | 22 | | PA | | 16-0 | SPARE | D04870P | | 44 | | | | D05352P | 48 | | ALL |
| 033 | 20 | | PA | | 23-0 | 33-26-11 | D05346P | | 9 | | | | D04870P | 32 | | ALL |
| 035 | 22 | | PA | | 16-0 | 36-11-41 | D04870P | | 19 | | | | D05352P | 19 | | ALL |
| 036 | 22 | | PA | | 16-0 | SPARE | D04870P | | 43 | | | | D05352P | 49 | | ALL |
| 038 | 24 | | PK | | 26-0 | 21-26-21 | D04870P | | 38 | | | | D06252P | 5 | | ALL |
| 039 | 24 | | PK | | 26-0 | 21-44-21 | D04870P | | 21 | | | | D06252P | 6 | | ALL |
| 040 | 24 | | PK | | 16-0 | 21-26-21 | D04870P | | 37 | | | | D05352P | 2 | | ALL |
| 041 | 22 | | PA | | 16-0 | 21-26-21 | D04870P | | 23 | | | | D05352P | 3 | | ALL |
| 042 | 24 | | PK | | 16-0 | 21-44-21 | D04870P | | 24 | | | | D05352P | 23 | | ALL |
| 043 | 24 | | PK | | 16-0 | 21-44-21 | D04870P | | 25 | | | | D05352P | 24 | | ALL |
| 045 | 24 | | PK | | 30-0 | 21-44-21 | D04870P | | 27 | | | | D05348P | 30 | | ALL |
| 046 | 22 | | PA | | 26-0 | 21-44-21 | D04870P | | 28 | | | | D06252P | 7 | | ALL |
| 049 | 18 | | PA | | 30-0 | SPARE | D04870P | | 41 | DL | | | D05348P | 41 | DK | 280-299 |
| 050 | 22 | | PQ | B | 16-0 | 29-11-12 | D04870P | | 3 | | | | D05352P | 21 | | ALL |
| 050Z | | | | B | 0-0 | 29-11-12 | D04870P | | | DED | | | D05352P | DED | | ALL |
| 051 | 24 | | PK | | 26-0 | 21-26-21 | D04870P | | 22 | | | | D06252P | 8 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1200

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1204 | 286T1204 | | | PANEL AREA FEEDER (continued) | | | | | | | | | | | |
| 053 | 16 | | PA | | 17-0 | 33-45-11 | D05352P | 16 | FL | | D05348P | 23 | FM | | ALL |
| 054 | 16 | | PA | | 17-0 | 33-45-11 | D05352P | 17 | FL | | D05348P | 24 | FM | | ALL |
| 057 | 24 | | PK | | 17-0 | SPARE | D05352P | 54 | | | D05348P | 37 | | | ALL |
| 058 | 24 | | PK | | 17-0 | SPARE | D05352P | 55 | | | D05348P | 39 | | | ALL |
| 059 | 24 | | PK | | 17-0 | SPARE | D05352P | 53 | | | D05348P | 36 | | | 050-099, 151, 162-199, 275-299 |
| 059 | 24 | | PK | | 17-0 | 21-66-41 | D05352P | 53 | | | D05348P | 36 | | | 150, 152-157 |
| 060 | 20 | | PA | | 14-0 | 30-81-11 | D06252P | 3 | | | D05352P | 22 | | | 050-099, 150-199 |
| 062 | 24 | | PK | | 14-0 | 21-51-13 | D06252P | 11 | | | D05352P | 29 | | | ALL |
| 063 | 24 | | PK | | 26-0 | SPARE | D04870P | | CAP | Y | D06252P | 1 | | | ALL |
| 064 | 24 | | PK | | 30-0 | 21-58-16 | D04870P | 34 | | | D05348P | 3 | | | ALL |
| 065 | 22 | | PA | | 26-0 | SPARE | D04870P | 48 | | | D06252P | | CAP | Y | 150-154 |
| 065 | 22 | | PA | | 26-0 | SPARE | D04870P | 48 | | | D06252P | 3 | | | 275-299 |
| 068 | 20 | | PA | | 30-0 | 25-31-11 | D05348P | 40 | | | D04870P | 40 | | | 050-099, 150-199, 275-278 |
| 068 | 18 | | PA | | 30-0 | 25-31-11 | D05348P | 40 | DK | | D04870P | 40 | DL | | 280-299 |
| 071 | 24 | | PK | | 13-0 | 21-44-21 | D06252P | 9 | | | D05348P | 29 | | | ALL |
| 072 | 24 | | PK | | 13-0 | 21-44-21 | D06252P | 10 | | | D05348P | 31 | | | ALL |
| 073 | 24 | | PK | | 14-0 | 21-51-21 | D05352P | 28 | | | D06252P | 14 | | | ALL |
| 074 | 16 | | PA | | 10-0 | 30-71-24 | D05346P | 7 | | | D05352P | 40 | | | 050-099, 150-199 |
| 078 | 24 | | PK | | 14-0 | 21-53-21 | D06252P | 17 | | | D05352P | 32 | | | ALL |
| 079 | 24 | | PK | | 14-0 | 21-53-21 | D06252P | 18 | | | D05352P | 33 | | | ALL |
| 080 | 24 | | PK | | 14-0 | 21-53-21 | D06252P | 19 | | | D05352P | 34 | | | ALL |
| 081 | 24 | | PK | | 14-0 | 21-53-21 | D06252P | 20 | | | D05352P | 35 | | | ALL |
| 082 | 24 | | PK | | 14-0 | 21-53-21 | D06252P | 21 | | | D05352P | 36 | | | ALL |
| 083 | 24 | | PK | | 14-0 | 21-53-21 | D06252P | 22 | | | D05352P | 37 | | | ALL |
| 084 | 24 | | PK | | 12-0 | 21-51-13 | D06262J | 1 | | | D06252P | 12 | | | ALL |
| 085 | 24 | | PK | | 12-0 | 21-51-13 | D06262J | 2 | | | D06252P | 13 | | | ALL |
| 086 | 24 | | PK | | 12-0 | 21-51-13 | D06262J | 3 | | | D06252P | 23 | | | ALL |
| 087 | 24 | | PK | | 30-0 | 27-38-11 | D04870P | 31 | | | D05348P | 38 | | | ALL |
| 088 | 20 | | PA | | 3-0 | 21-51-13 | D06262J | 8 | | | GD00754 | A.. | 2 | | ALL |
| 089 | 20 | | PA | | 3-0 | 21-51-13 | D06262J | 9 | | | GD00754 | S.. | 2 | | ALL |
| 095 | 24 | | PK | | 26-0 | 36-11-41 | D04870P | 55 | | | D06252P | 2 | | | ALL |
| 096 | 24 | | PK | | 13-0 | 33-16-14 | D05348P | 25 | | | D06252P | 4 | | | ALL |
| 097 | 22 | | PA | | 16-0 | 21-58-16 | D04870P | 54 | | | D05352P | 52 | | | ALL |
| 098 | 24 | | PK | | 16-0 | 36-11-41 | D04870P | 46 | | | D05352P | 30 | | | ALL |
| 099 | 24 | | PK | | 16-0 | 36-11-41 | D04870P | 45 | | | D05352P | 31 | | | ALL |
| 101 | 18 | | PA | | 35-0 | 38-32-11 | D04870P | 47 | DL | | D05348P | 22 | DK | | 275-276 |
| 107 | 24 | | PK | | 30-0 | 21-58-16 | D04870P | 35 | | | D05348P | 26 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1200

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|--|-------|------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-----|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1204 | 286T1204 | PANEL AREA FEEDER (continued) | | | | | | | | | | | | | | |
| 108 | 24 | | PK | 30-0 | 21-58-16 | D04870P | | 50 | | | | | D05348P | 28 | | ALL |
| 114 | 20 | | PA | 14-0 | 30-71-24 | D06252P | | 24 | | | | | D05352P | 20 | | 050-099, 150-199 |
| 115 | 20 | | PA | 23-0 | 33-26-11 | D05346P | | 12 | | | | | D04870P | 4 | | 050-099, 150-199 |
| 203B | 22 | | PB C | 5-0 | 21-51-13 | D06262J | | 4 | | | | | D05352P | 1 | | ALL |
| 203R | 22 | | PB C | 0-0 | 21-51-13 | D06262J | | 5 | | | | | D05352P | 25 | | ALL |
| 204B | 22 | | PB D | 5-0 | 21-51-13 | D06262J | | 6 | | | | | D05352P | 38 | | ALL |
| 204R | 22 | | PB D | 0-0 | 21-51-13 | D06262J | | 7 | | | | | D05352P | 39 | | ALL |
| 208B | 24 | | PL A | 14-0 | 21-51-21 | D05352P | | 26 | | | | | D06252P | 16 | | ALL |
| 208R | 24 | | PL A | 0-0 | 21-51-21 | D05352P | | 27 | | | | | D06252P | 15 | | ALL |
| W1205 | 286T1205 | ELEC SPOILER CONT PCA 4,W/W DISC TO WING DISC | | | | | | | | | | | | | | |
| 001 | 20 | | UA | 1-0 | 27-61-16 | SM00001 | | | | W | | | D05465J | 2 | | ALL |
| 002 | 20 | | UA | 1-0 | 27-61-16 | SM00002 | | | | W | | | D05465J | 4 | | ALL |
| 003 | 20 | | UA | 1-0 | 27-61-16 | SM00001 | | | | W | | | D05465J | 1 | | ALL |
| 004 | 20 | | UA | 1-0 | 27-61-16 | SM00002 | | | | W | | | D05465J | 3 | | ALL |
| 005 | 18 | | UA | 2-0 | 27-61-16 | GD00453 | | | S.. | N | | | D05465J | 10 | | ALL |
| WBK | 20 | | 7N 1B | 41-0 | 27-61-16 | D05211J | | 2 | | | | | D05465J | 8 | | ALL |
| WBKZ | | | 1B | 0-0 | 27-61-16 | GD00429 | | | S.. | N | | | GD00453 | S.. | N | ALL |
| WBN | 20 | | 7N 1B | 0-0 | 27-61-16 | D05211J | | 6 | | | | | D05465J | 6 | | ALL |
| WBU | 20 | | 7N 1B | 0-0 | 27-61-16 | D05211J | | 3 | | | | | SM00002 | | W | ALL |
| WOR | 20 | | 7N 1B | 0-0 | 27-61-16 | D05211J | | 5 | | | | | D05465J | 5 | | ALL |
| WRB | 20 | | 7N 1B | 0-0 | 27-61-16 | D05211J | | 7 | | | | | D05465J | 7 | | ALL |
| WRD | 20 | | 7N 1B | 0-0 | 27-61-16 | D05211J | | 1 | | | | | SM00001 | | W | ALL |
| WVI | 20 | | 7N 1B | 0-0 | 27-61-16 | D05211J | | 4 | | | | | D05465J | 9 | | ALL |
| W1206 | 286T1206 | AUTOBRAKE METERED PRESS SW | | | | | | | | | | | | | | |
| 002 | 20 | | UA | 4-0 | 32-42-12 | D04770P | | 2 | | | | | D02192 | 3 | | ALL |
| 003 | 20 | | UA | 4-0 | 32-42-12 | D04770P | | 3 | | | | | D02192 | 2 | | ALL |
| 201B | 20 | | VG B | 7-0 | 31-31-22 | D04770P | | 5 | | | | | D02291 | 3 | | ALL |
| 201R | 20 | | VG B | 0-0 | 31-31-22 | D04770P | | 4 | | | | | D02291 | 2 | | ALL |
| 201Z | | | B | 0-0 | 31-31-22 | D04770P | | 6 | | | | | D02291 | | DED | ALL |
| 202 | 20 | | UA | 7-0 | 31-31-22 | D04770P | | 7 | | | | | D02291 | 1 | | ALL |
| W1207 | 286T1207 | ELEC SPOILER CONT PCA 5,W/W DISC TO WING DISC | | | | | | | | | | | | | | |
| 001 | 20 | | UA | 0-7 | 27-61-17 | SM00001 | | | | W | | | D05467J | 2 | | ALL |
| 002 | 20 | | UA | 0-7 | 27-61-17 | SM00002 | | | | W | | | D05467J | 4 | | ALL |
| 003 | 20 | | UA | 0-7 | 27-61-17 | SM00001 | | | | W | | | D05467J | 1 | | ALL |
| 004 | 20 | | UA | 0-7 | 27-61-17 | SM00002 | | | | W | | | D05467J | 3 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1200

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1207 | 286T1207 | | | ELEC SPOILER CONT PCA 5,W/W DISC TO WING DISC (continued) | | | | | | | | | | | |
| 005 | 18 | | UA | | 1-6 | 27-61-17 | GD00439 | S.. | N | | D05467J | 10 | | | ALL |
| WBK | 20 | | 7N | 1B | 31-2 | 27-61-17 | D05235J | 2 | | | D05467J | 8 | | | ALL |
| WBKZ | | | | 1B | 0-0 | 27-61-17 | GD00415 | S.. | N | | GD00439 | S.. | N | | ALL |
| WBN | 20 | | 7N | 1B | 0-0 | 27-61-17 | D05235J | 6 | | | D05467J | 6 | | | ALL |
| WBU | 20 | | 7N | 1B | 0-0 | 27-61-17 | D05235J | 3 | | | SM00002 | | W | | ALL |
| WOR | 20 | | 7N | 1B | 0-0 | 27-61-17 | D05235J | 5 | | | D05467J | 5 | | | ALL |
| WRB | 20 | | 7N | 1B | 0-0 | 27-61-17 | D05235J | 7 | | | D05467J | 7 | | | ALL |
| WRD | 20 | | 7N | 1B | 0-0 | 27-61-17 | D05235J | 1 | | | SM00001 | | W | | ALL |
| WVI | 20 | | 7N | 1B | 0-0 | 27-61-17 | D05235J | 4 | | | D05467J | 9 | | | ALL |
| W1208 | 286T1208 | | | RAM AIR TURBINE MOTOR SUPPLY | | | | | | | | | | | |
| 001 | 08 | | HA | | 4-0 | 29-21-31 | TB5014 | 3 | G | | SM00001 | | GE | | 050-099 |
| 001 | 08 | | HA | | 3-0 | 29-21-31 | TB5014 | 3 | G | | SM00001 | | GE | | 150-199, 275-299 |
| 002 | 06 | | QY | | 91-0 | 29-21-31 | SM00002 | | GE | | SM00001 | | GE | | 050-099 |
| 002 | 06 | | QY | | 100-0 | 29-21-31 | SM00002 | | GE | | SM00001 | | GE | | 150-199, 275-299 |
| 003 | 08 | | HA | | 3-0 | 29-21-31 | K00234 | A1 | R | * | K00235 | A1 | R | * | ALL |
| 004 | 08 | | HA | | 3-0 | 29-21-31 | K00236 | A1 | R | | K00235 | A1 | R | * | ALL |
| 005 | 08 | | HA | | 6-0 | 29-21-31 | D02352 | B | | | K00234 | A2 | R | | ALL |
| 006 | 08 | | HA | | 6-0 | 29-21-31 | D02352 | A | | | K00235 | A2 | R | * | ALL |
| 007 | 08 | | HA | | 3-0 | 29-21-31 | K00236 | A2 | R | | K00235 | A2 | R | * | ALL |
| 008 | 08 | | HA | | 5-0 | 29-21-31 | D02352 | C | | | GD00024 | D.. | E | | ALL |
| 009 | 08 | | HA | | 5-0 | 29-21-31 | D02352 | D | | | GD04202 | S.. | E | | ALL |
| 010 | 08 | | HA | | 5-0 | 29-21-31 | SM00002 | | GE | | K00234 | A1 | R | * | ALL |
| W1209 | 286T1209 | | | ELEC SPOILER CONT-PCA 6,W.W DISC TO WING DISC | | | | | | | | | | | |
| 001 | 20 | | UA | | 1-0 | 27-61-18 | SM00001 | | W | | D05469J | 2 | | | ALL |
| 002 | 20 | | UA | | 1-0 | 27-61-18 | SM00002 | | W | | D05469J | 4 | | | ALL |
| 003 | 20 | | UA | | 1-0 | 27-61-18 | SM00001 | | W | | D05469J | 1 | | | ALL |
| 004 | 20 | | UA | | 1-0 | 27-61-18 | SM00002 | | W | | D05469J | 3 | | | ALL |
| 005 | 18 | | UA | | 2-0 | 27-61-18 | GD00455 | S.. | N | | D05469J | 10 | | | ALL |
| WBK | 20 | | 7N | 1B | 19-0 | 27-61-18 | D05237J | 2 | | | D05469J | 8 | | | ALL |
| WBKZ | | | | 1B | 0-0 | 27-61-18 | GD00431 | S.. | N | | GD00455 | S.. | N | | ALL |
| WBN | 20 | | 7N | 1B | 0-0 | 27-61-18 | D05237J | 6 | | | D05469J | 6 | | | ALL |
| WBU | 20 | | 7N | 1B | 0-0 | 27-61-18 | D05237J | 3 | | | SM00002 | | W | | ALL |
| WOR | 20 | | 7N | 1B | 0-0 | 27-61-18 | D05237J | 5 | | | D05469J | 5 | | | ALL |
| WRB | 20 | | 7N | 1B | 0-0 | 27-61-18 | D05237J | 7 | | | D05469J | 7 | | | ALL |
| WRD | 20 | | 7N | 1B | 0-0 | 27-61-18 | D05237J | 1 | | | SM00001 | | W | | ALL |
| WVI | 20 | | 7N | 1B | 0-0 | 27-61-18 | D05237J | 4 | | | D05469J | 9 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1200
Page 5 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1210 | 286T1210 | | | ELEC PUMP 1 PRESS SW | | | | | | | | | | | | |
| 002 | 18 | | UA | 12-0 | 29-11-31 | D05358P | | 2 | | | D00474 | | 2 | | 050-099 | |
| 002 | 18 | | UA | 11-4 | 29-11-31 | D05358P | | 2 | | | D00474 | | 2 | | 150-199, 275-299 | |
| 003 | 18 | | UA | 12-0 | 29-11-31 | D05358P | | 3 | | | D00474 | | 3 | | 050-099 | |
| 003 | 18 | | UA | 11-4 | 29-11-31 | D05358P | | 3 | | | D00474 | | 3 | | 150-199, 275-299 | |
| 301B | 18 | | UC AA | 16-0 | 29-11-31 | D05358P | | 7 | | | D00918 | | 1 | | 050-099 | |
| 301B | 18 | | UC AA | 11-2 | 29-11-31 | D05358P | | 7 | | | D00918 | | 1 | | 150-199, 275-299 | |
| 301R | 18 | | UC AA | 0-0 | 29-11-31 | D05358P | | 1 | | | D00918 | | 2 | | ALL | |
| 301Y | 18 | | UC AA | 0-0 | 29-11-31 | D05358P | | 4 | | | D00918 | | 3 | | ALL | |
| W1211 | 286T1211 | | | ELEC SPOILER CONT PCA 7,W/W DISC TO WING DISC | | | | | | | | | | | | |
| 001 | 20 | | UA | 1-0 | 27-61-18 | SM00001 | | | W | | D05471J | | 2 | | ALL | |
| 002 | 20 | | UA | 1-0 | 27-61-18 | SM00002 | | | W | | D05471J | | 4 | | ALL | |
| 003 | 20 | | UA | 1-0 | 27-61-18 | SM00001 | | | W | | D05471J | | 1 | | ALL | |
| 004 | 20 | | UA | 1-0 | 27-61-18 | SM00002 | | | W | | D05471J | | 3 | | ALL | |
| 005 | 18 | | UA | 2-0 | 27-61-18 | GD00461 | | S.. | N | | D05471J | | 10 | | ALL | |
| WBK | 20 | | 7N 1B | 23-0 | 27-61-18 | D05239J | | 2 | | | D05471J | | 8 | | ALL | |
| WBKZ | | | | 0-0 | 27-61-18 | GD00437 | | S.. | N | | GD00461 | | S.. | N | ALL | |
| WBN | 20 | | 7N 1B | 0-0 | 27-61-18 | D05239J | | 6 | | | D05471J | | 6 | | ALL | |
| WBU | 20 | | 7N 1B | 0-0 | 27-61-18 | D05239J | | 3 | | | SM00002 | | | W | ALL | |
| WOR | 20 | | 7N 1B | 0-0 | 27-61-18 | D05239J | | 5 | | | D05471J | | 5 | | ALL | |
| WRB | 20 | | 7N 1B | 0-0 | 27-61-18 | D05239J | | 7 | | | D05471J | | 7 | | ALL | |
| WRD | 20 | | 7N 1B | 0-0 | 27-61-18 | D05239J | | 1 | | | SM00001 | | | W | ALL | |
| WVI | 20 | | 7N 1B | 0-0 | 27-61-18 | D05239J | | 4 | | | D05471J | | 9 | | ALL | |
| W1212 | 286T1212 | | | PARKING BRAKE VALVE | | | | | | | | | | | | |
| 001 | 18 | | UA | 7-4 | 32-41-11 | D04988P | | 1 | | | D02228 | | 3 | | ALL | |
| 002 | 18 | | UA | 7-4 | 32-41-11 | D04988P | | 2 | | | D02228 | | 2 | | ALL | |
| 015 | 18 | | UA | 6-4 | 29-11-32 | D04988P | | 7 | | | D00464 | | 3 | | ALL | |
| 016 | 18 | | UA | 6-4 | 29-11-32 | D04988P | | 8 | | | D00464 | | 2 | | ALL | |
| 017 | 20 | | UA | 6-7 | 29-11-32 | D04988P | | 9 | | | D00466 | | 3 | | ALL | |
| 018 | 20 | | UA | 6-7 | 29-11-32 | D04988P | | 10 | | | D00466 | | 2 | | ALL | |
| 019 | 20 | | UA | 6-7 | 29-11-32 | D04988P | | 11 | | | D00466 | | 1 | | ALL | |
| 020 | 18 | | UA | 5-1 | 29-32-11 | D04988P | | 3 | | | D02216 | | 1 | | ALL | |
| 021 | 18 | | UA | 5-1 | 29-32-11 | D04988P | | 4 | | | D02216 | | 2 | | ALL | |
| 024 | 18 | | UA | 5-1 | 29-32-11 | D04988P | | 12 | | | D02216 | | 3 | | ALL | |
| W1213 | 286T1213 | | | ELEC SPOILER CONT PCA 8,W/W DISC TO WING DISC | | | | | | | | | | | | |
| 001 | 20 | | UA | 0-7 | 27-61-17 | SM00001 | | | W | | D05473J | | 2 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1210

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1213 | 286T1213 | | | ELEC SPOILER CONT PCA 8,W/W DISC TO WING DISC (continued) | | | | | | | | | | | |
| 002 | 20 | | UA | | 0-7 | 27-61-17 | SM00002 | | W | | D05473J | | 4 | | ALL |
| 003 | 20 | | UA | | 0-7 | 27-61-17 | SM00001 | | W | | D05473J | | 1 | | ALL |
| 004 | 20 | | UA | | 0-7 | 27-61-17 | SM00002 | | W | | D05473J | | 3 | | ALL |
| 005 | 18 | | UA | | 1-4 | 27-61-17 | GD00445 | S.. | N | | D05473J | | 10 | | ALL |
| WBK | 20 | | 7N | 1B | 27-2 | 27-61-17 | D05241J | | 2 | | D05473J | | 8 | | ALL |
| WBKZ | | | | 1B | 0-0 | 27-61-17 | GD00421 | S.. | N | | GD00445 | S.. | N | | ALL |
| WBN | 20 | | 7N | 1B | 0-0 | 27-61-17 | D05241J | | 6 | | D05473J | | 6 | | ALL |
| WBU | 20 | | 7N | 1B | 0-0 | 27-61-17 | D05241J | | 3 | | SM00002 | | | W | ALL |
| WOR | 20 | | 7N | 1B | 0-0 | 27-61-17 | D05241J | | 5 | | D05473J | | 5 | | ALL |
| WRB | 20 | | 7N | 1B | 0-0 | 27-61-17 | D05241J | | 7 | | D05473J | | 7 | | ALL |
| WRD | 20 | | 7N | 1B | 0-0 | 27-61-17 | D05241J | | 1 | | SM00001 | | | W | ALL |
| WVI | 20 | | 7N | 1B | 0-0 | 27-61-17 | D05241J | | 4 | | D05473J | | 9 | | ALL |
| W1214 | 286T1214 | | | LEFT METERED PRESS SW | | | | | | | | | | | |
| 002 | 20 | | UA | | 2-10 | 32-42-12 | D05586P | | 1 | | D02190 | | 3 | | ALL |
| 003 | 20 | | UA | | 2-10 | 32-42-12 | D05586P | | 3 | | D02190 | | 2 | | ALL |
| 201B | 20 | | VG | A | 7-4 | 31-31-22 | D05586P | | 6 | | D02293 | | 3 | | ALL |
| 201R | 20 | | VG | A | 0-0 | 31-31-22 | D05586P | | 5 | | D02293 | | 2 | | ALL |
| 201Z | | | | A | 0-0 | 31-31-22 | D05586P | | 7 | | D02293 | DED | | | ALL |
| 202 | 20 | | UA | | 7-4 | 31-31-22 | D05586P | | 2 | | D02293 | | 1 | | ALL |
| W1215 | 286T1215 | | | ELEC SPOILER CONT-PCA 9,W/W DISC TO WING DISC | | | | | | | | | | | |
| 001 | 20 | | UA | | 0-7 | 27-61-16 | SM00001 | | W | | D05475J | | 2 | | ALL |
| 002 | 20 | | UA | | 0-7 | 27-61-16 | SM00002 | | W | | D05475J | | 4 | | ALL |
| 003 | 20 | | UA | | 0-7 | 27-61-16 | SM00001 | | W | | D05475J | | 1 | | ALL |
| 004 | 20 | | UA | | 0-7 | 27-61-16 | SM00002 | | W | | D05475J | | 3 | | ALL |
| 005 | 18 | | UA | | 1-5 | 27-61-16 | GD00459 | S.. | N | | D05475J | | 10 | | ALL |
| WBK | 20 | | 7N | 1B | 38-6 | 27-61-16 | D05221J | | 2 | | D05475J | | 8 | | ALL |
| WBKZ | | | | 1B | 0-0 | 27-61-16 | GD00435 | S.. | N | | GD00459 | S.. | N | | ALL |
| WBN | 20 | | 7N | 1B | 0-0 | 27-61-16 | D05221J | | 6 | | D05475J | | 6 | | ALL |
| WBU | 20 | | 7N | 1B | 0-0 | 27-61-16 | D05221J | | 3 | | SM00002 | | | W | ALL |
| WOR | 20 | | 7N | 1B | 0-0 | 27-61-16 | D05221J | | 5 | | D05475J | | 5 | | ALL |
| WRB | 20 | | 7N | 1B | 0-0 | 27-61-16 | D05221J | | 7 | | D05475J | | 7 | | ALL |
| WRD | 20 | | 7N | 1B | 0-0 | 27-61-16 | D05221J | | 1 | | SM00001 | | | W | ALL |
| WVI | 20 | | 7N | 1B | 0-0 | 27-61-16 | D05221J | | 4 | | D05475J | | 9 | | ALL |
| W1216 | 286T1216 | | | P61 TO P19 FEEDER | | | | | | | | | | | |
| 001 | 16 | | PA | | 27-6 | 33-26-21 | D05180P | | 1 | FL | D05178P | | 1 | FM | ALL |

WIRE LIST
D280T132

91-21-11
Section W1210
Page 2
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1216 | 286T1216 | | | P61 TO P19 FEEDER (continued) | | | | | | | | | | | | | |
| 006 | 24 | | PK | 27-6 | 35-21-11 | D05180P | | 6 | | | | | D05178P | 6 | | | ALL |
| 007 | 22 | | PA | 27-6 | 33-26-11 | D05180P | | 7 | | | | | D05178P | 7 | | | ALL |
| 008 | 20 | | PA | 27-6 | SPARE | D05180P | | 8 | | | | | D05178P | 8 | | | ALL |
| 009 | 22 | | PA | 27-6 | 33-25-11 | D05180P | | 9 | | | | | D05178P | 9 | | | ALL |
| 010 | 18 | | PA | 27-6 | 26-13-11 | D05180P | | 35 | DL | | | | D05178P | 19 | DK | | 050-099, 150-199 |
| 013 | 22 | | PA | 27-6 | 21-66-11 | D05180P | | 36 | | | | | D05178P | 18 | | | 050-099, 162-199 |
| 017 | 24 | | PK | 27-6 | 33-24-11 | D05178P | | 17 | | | | | D05180P | 17 | | | ALL |
| 018 | 24 | | PK | 27-6 | 21-24-11 | D05180P | | 12 | | | | | D05178P | 2 | | | 050-099, 150-199 |
| 020 | 24 | | PK | 27-6 | 52-51-11 | D05180P | | 20 | | | | | D05178P | 20 | | | ALL |
| 021 | 22 | | PA | 27-6 | 52-51-11 | D05180P | | 21 | | | | | D05178P | 21 | | | ALL |
| 022 | 22 | | PA | 27-6 | 33-51-11 | D05180P | | 19 | | | | | D05178P | 22 | | | ALL |
| 024 | 22 | | PA | 1-0 | 21-45-21 | D05180P | | 24 | | | | | SM00002 | | S | | 050-099, 150-156, 162-166, 275-276 |
| 024 | 20 | | PA | 1-0 | 21-45-21 | D05180P | | 24 | | | | | SM00002 | 9 | | | 157, 167-199, 277-299 |
| 025 | 22 | | PA | 29-6 | 21-45-21 | D10742 | | 2 | | | | | SM00002 | | S | | 050-099, 150-156, 162-166 |
| 025 | 20 | | PA | 29-6 | 21-45-21 | D10742 | | 2 | | | | | SM00002 | 9 | | | 157, 167-199 |
| 025 | 22 | | PA | 29-6 | 21-45-21 | STA0362 | | | CAP | Y | | | SM00002 | | S | | 275-276 |
| 025 | 20 | | PA | 29-6 | 21-45-21 | STA0362 | | | CAP | Y | | | SM00002 | 9 | | | 277-299 |
| 026 | 22 | | PA | 27-6 | 21-45-21 | D10740 | | 2 | | | | | SM00002 | | S | | 050-099, 150-156, 162-166, 275-276 |
| 026 | 20 | | PA | 27-6 | 21-45-21 | D10740 | | 2 | | | | | SM00002 | 9 | | | 157, 167-199, 277-299 |
| 027 | 22 | | PA | 29-6 | 21-45-21 | D10742 | | 1 | | | | | SM00001 | | S | | 050-099, 150-156, 162-166 |
| 027 | 20 | | PA | 29-6 | 21-45-21 | D10742 | | 1 | | | | | SM00001 | 9 | | | 157, 167-199 |
| 027 | 22 | | PA | 29-6 | 21-45-21 | STA0362 | | | CAP | Y | | | SM00001 | | S | | 275-276 |
| 027 | 20 | | PA | 29-6 | 21-45-21 | STA0362 | | | CAP | Y | | | SM00001 | 9 | | | 277-299 |
| 028 | 22 | | PA | 1-0 | 21-45-21 | D05180P | | 22 | | | | | SM00001 | | S | | 050-099, 150-156, 162-166, 275-276 |
| 028 | 20 | | PA | 1-0 | 21-45-21 | D05180P | | 22 | | | | | SM00001 | 9 | | | 157, 167-199, 277-299 |
| 029 | 22 | | PA | 27-6 | 21-45-21 | D10740 | | 1 | | | | | SM00001 | | S | | 050-099, 150-156, 162-166, 275-276 |
| 029 | 20 | | PA | 27-6 | 21-45-21 | D10740 | | 1 | | | | | SM00001 | 9 | | | 157, 167-199, 277-299 |
| 030 | 20 | | PA | 5-0 | 21-45-21 | D10742 | | 3 | | | | | GD01114 | S.. | 2 | | 050-099, 150-199 |
| 030 | 20 | | PA | 5-0 | 21-45-21 | STA0362 | | | CAP | Y | | | GD01114 | S.. | 2 | | 275-299 |
| 031 | 20 | | PA | 5-0 | 21-45-21 | D10740 | | 3 | | | | | GD03932 | S.. | 2 | | ALL |
| 032 | 20 | | PA | 29-6 | 21-45-21 | D10742 | | 4 | | | | | SM00001 | | 9 | | 157, 167-199 |
| 032 | 20 | | PA | 29-6 | 21-45-21 | STA0362 | | | CAP | Y | | | SM00001 | | 9 | | 277-299 |
| 033 | 20 | | PA | 27-6 | 21-45-21 | D10740 | | 4 | | | | | SM00001 | | 9 | | 157, 167-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W1210

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|---|----|------|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1216 | 286T1216 | P61 TO P19 FEEDER (continued) | | | | | | | | | | | | | |
| 201B | 24 | PL | A | 27-6 | 21-61-21 | D05180P | | 2 | | D05178P | 12 | | | ALL | |
| 201R | 24 | PL | A | 0-0 | 21-61-21 | D05180P | | 3 | | D05178P | 3 | | | ALL | |
| 202B | 24 | PL | B | 27-6 | 21-61-21 | D05180P | | 4 | | D05178P | 4 | | | ALL | |
| 202R | 24 | PL | B | 0-0 | 21-61-21 | D05180P | | 5 | | D05178P | 5 | | | ALL | |
| 204B | 20 | PB | D | 27-6 | 21-65-11 | D05180P | | 13 | | D05178P | 13 | | | ALL | |
| 204R | 20 | PB | D | 0-0 | 21-65-11 | D05180P | | 14 | | D05178P | 14 | | | ALL | |
| 205B | 22 | PB | E | 27-6 | 21-51-12 | D05178P | | 15 | | D05180P | 15 | | | ALL | |
| 205R | 22 | PB | E | 0-0 | 21-51-12 | D05178P | | 16 | | D05180P | 16 | | | ALL | |
| 206B | 24 | PL | IF | 27-6 | 21-61-61 | D05180P | | 11 | | D05178P | 11 | | | ALL | |
| 206R | 24 | PL | IF | 0-0 | 21-61-61 | D05180P | | 10 | | D05178P | 10 | | | ALL | |
| 207B | 24 | PL | IG | 47-5 | 21-61-61 | D05180P | | 26 | | D13462 | 1 | | | ALL | |
| 207R | 24 | PL | IG | 0-0 | 21-61-61 | D05180P | | 25 | | D13462 | 2 | | | ALL | |
| 208B | 24 | PL | IH | 27-6 | 21-61-71 | D05180P | | 27 | | D05178P | 24 | | | ALL | |
| 208R | 24 | PL | IH | 0-0 | 21-61-71 | D05180P | | 28 | | D05178P | 25 | | | ALL | |
| 209B | 24 | PL | II | 27-6 | 21-61-71 | D05180P | | 30 | | D05178P | 27 | | | ALL | |
| 209R | 24 | PL | II | 0-0 | 21-61-71 | D05180P | | 29 | | D05178P | 26 | | | ALL | |
| 210B | 20 | PB | IJ | 27-6 | 21-65-11 | D05180P | | 31 | | D05178P | 28 | | | ALL | |
| 210R | 20 | PB | IJ | 0-0 | 21-65-11 | D05180P | | 32 | | D05178P | 29 | | | ALL | |
| 211B | 20 | PB | IK | 27-6 | 21-65-11 | D05180P | | 33 | | D05178P | 30 | | | ALL | |
| 211R | 20 | PB | IK | 0-0 | 21-65-11 | D05180P | | 34 | | D05178P | 31 | | | ALL | |
| W1217 | 286T1217 | ELEC SPOILER CONT PCA 10,W/W DISC TO WING DISC | | | | | | | | | | | | | |
| 001 | 20 | UA | | 0-7 | 27-61-15 | SM00001 | | | W | D05477J | 2 | | | ALL | |
| 002 | 20 | UA | | 0-7 | 27-61-15 | SM00002 | | | W | D05477J | 4 | | | ALL | |
| 003 | 20 | UA | | 0-7 | 27-61-15 | SM00001 | | | W | D05477J | 1 | | | ALL | |
| 004 | 20 | UA | | 0-7 | 27-61-15 | SM00002 | | | W | D05477J | 3 | | | ALL | |
| 005 | 18 | UA | | 1-5 | 27-61-15 | GD00447 | | S.. | N | D05477J | 10 | | | ALL | |
| WBK | 20 | 7N | 1B | 47-0 | 27-61-15 | D05219J | | 2 | | D05477J | 8 | | | ALL | |
| WBKZ | | | 1B | 0-0 | 27-61-15 | GD00423 | | S.. | N | GD00447 | S.. | N | | ALL | |
| WBN | 20 | 7N | 1B | 0-0 | 27-61-15 | D05219J | | 6 | | D05477J | 6 | | | ALL | |
| WBU | 20 | 7N | 1B | 0-0 | 27-61-15 | D05219J | | 3 | | SM00002 | | W | | ALL | |
| WOR | 20 | 7N | 1B | 0-0 | 27-61-15 | D05219J | | 5 | | D05477J | 5 | | | ALL | |
| WRB | 20 | 7N | 1B | 0-0 | 27-61-15 | D05219J | | 7 | | D05477J | 7 | | | ALL | |
| WRD | 20 | 7N | 1B | 0-0 | 27-61-15 | D05219J | | 1 | | SM00001 | | W | | ALL | |
| WVI | 20 | 7N | 1B | 0-0 | 27-61-15 | D05219J | | 4 | | D05477J | 9 | | | ALL | |
| W1219 | 286T1219 | ELEC SPOILER CONT PCA 11,W/W DISC TO WING DISC | | | | | | | | | | | | | |
| 001 | 20 | UA | | 0-7 | 27-61-14 | SM00001 | | | W | D05479J | 2 | | | ALL | |
| 002 | 20 | UA | | 0-7 | 27-61-14 | SM00002 | | | W | D05479J | 4 | | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W1210
Page 4
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1219 | 286T1219 | | | ELEC SPOILER CONT PCA 11,W/W DISC TO WING DISC (continued) | | | | | | | | | | | | |
| 003 | 20 | | UA | 0-7 | 27-61-14 | SM00001 | | | | W | | D05479J | 1 | | | ALL |
| 004 | 20 | | UA | 0-7 | 27-61-14 | SM00002 | | | | W | | D05479J | 3 | | | ALL |
| 005 | 18 | | UA | 1-5 | 27-61-14 | GD00449 | | | S.. | N | | D05479J | 10 | | | ALL |
| WBK | 20 | | 7N | 1B | 44-10 | 27-61-14 | D05217J | | | 2 | | D05479J | 8 | | | ALL |
| WBKZ | | | | 1B | 0-0 | 27-61-14 | GD00425 | | | S.. | N | GD00449 | S.. | N | | ALL |
| WBN | 20 | | 7N | 1B | 0-0 | 27-61-14 | D05217J | | | 6 | | D05479J | 6 | | | ALL |
| WBU | 20 | | 7N | 1B | 0-0 | 27-61-14 | D05217J | | | 3 | | SM00002 | | W | | ALL |
| WOR | 20 | | 7N | 1B | 0-0 | 27-61-14 | D05217J | | | 5 | | D05479J | 5 | | | ALL |
| WRB | 20 | | 7N | 1B | 0-0 | 27-61-14 | D05217J | | | 7 | | D05479J | 7 | | | ALL |
| WRD | 20 | | 7N | 1B | 0-0 | 27-61-14 | D05217J | | | 1 | | SM00001 | | W | | ALL |
| WVI | 20 | | 7N | 1B | 0-0 | 27-61-14 | D05217J | | | 4 | | D05479J | 9 | | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1220 | 286T1220 | | | MEDICAL OUTLETS | | | | | | | | | | | |
| 001 | 16 | | PA | | 6-0 | 25-29-12 | D13458 | | B | | GD05624 | S.. | H | | 050-099, 150-157 |
| 001 | 16 | | PA | | 5-5 | 25-29-12 | D13458 | | B | | GD05624 | S.. | H | | 162-199 |
| 001 | 16 | | PA | | 6-3 | 25-29-12 | D13458 | | B | | GD05624 | S.. | H | | 275-299 |
| 002 | 08 | | PA | | 0-18 | 25-29-12 | D13458 | | A | | SM00004 | | | 9 | ALL |
| 003 | 08 | | PA | | 6-0 | 25-29-12 | D13458 | | C | | GD05626 | D.. | H | | 050-099, 150-157 |
| 003 | 08 | | PA | | 5-2 | 25-29-12 | D13458 | | C | | GD05626 | D.. | H | | 162-199 |
| 003 | 08 | | PA | | 6-3 | 25-29-12 | D13458 | | C | | GD05626 | D.. | H | | 275-299 |
| 004 | 16 | | PA | | 10-0 | 25-29-12 | D13454 | | D | | GD02206 | S.. | E | | 050-099 |
| 004 | 16 | | PA | | 16-0 | 25-29-12 | D13454 | | D | | GD01582 | S.. | E | | 150-157 |
| 004 | 16 | | PA | | 18-0 | 25-29-12 | D13454 | | D | | GD01582 | S.. | E | | 162-199 |
| 004 | 16 | | PA | | 19-0 | 25-29-12 | D13454 | | D | | GD02202 | S.. | E | | 275-299 |
| 005 | 16 | | PA | | 7-0 | 25-29-12 | D13452 | | D | | GD02188 | S.. | E | | 050-099 |
| 005 | 16 | | PA | | 16-0 | 25-29-12 | D13452 | | D | | GD01578 | S.. | E | | 150-157, 275-299 |
| 005 | 16 | | PA | | 14-0 | 25-29-12 | D13452 | | D | | GD01578 | S.. | E | | 162-199 |
| 006 | 06 | | PA | | 52-0 | 25-29-12 | SM00004 | | | 9 | TB5010 | | F | 3 | 050-099 |
| 006 | 06 | | PA | | 54-0 | 25-29-12 | SM00004 | | | 9 | TB5010 | | F | 3 | 150-199 |
| 006 | 06 | | PA | | 54-5 | 25-29-12 | SM00004 | | | 9 | TB5010 | | F | 3 | 275-299 |
| 301B | 16 | | PS | C | 73-0 | 25-29-12 | D13456 | | D | | SM00002 | | | 9 | 050-099 |
| 301B | 16 | | PS | C | 72-0 | 25-29-12 | D13456 | | D | | SM00002 | | | 9 | 150-157 |
| 301B | 16 | | PS | C | 70-11 | 25-29-12 | D13456 | | D | | SM00002 | | | 9 | 162-199 |
| 301B | 16 | | PS | C | 73-9 | 25-29-12 | D13456 | | D | | SM00002 | | | 9 | 275-299 |
| 301R | 16 | | PS | C | 0-0 | 25-29-12 | D13456 | | E | | SM00001 | | | 9 | ALL |
| 301Y | 16 | | PS | C | 0-0 | 25-29-12 | D13456 | | B | | SM00003 | | | 9 | ALL |
| 301Z | | | | C | 0-0 | 25-29-12 | D13456 | | C | | SM00001 | REF | | 9 | ALL |
| 302B | 16 | | PS | A | 13-0 | 25-29-12 | D13454 | | A | | SM00002 | | | 9 | 050-099 |
| 302B | 16 | | PS | A | 12-0 | 25-29-12 | D13454 | | A | | SM00002 | | | 9 | 150-157 |
| 302B | 16 | | PS | A | 11-7 | 25-29-12 | D13454 | | A | | SM00002 | | | 9 | 162-199 |
| 302B | 16 | | PS | A | 1-0 | 25-29-12 | D13454 | | A | | SM00002 | | | 9 | 275-299 |
| 302R | 16 | | PS | A | 0-0 | 25-29-12 | D13454 | | C | | SM00001 | | | 9 | ALL |
| 302Y | 16 | | PS | A | 0-0 | 25-29-12 | D13454 | | B | | SM00003 | | | 9 | ALL |
| 302Z | | | | A | 0-0 | 25-29-12 | D13454 | | DED | | SM00001 | REF | | 9 | ALL |
| 303B | 16 | | PS | B | 84-0 | 25-29-12 | D13452 | | A | | SM00002 | | | 9 | 050-099 |
| 303B | 16 | | PS | B | 109-0 | 25-29-12 | D13452 | | A | | SM00002 | | | 9 | 150-157 |
| 303B | 16 | | PS | B | 107-3 | 25-29-12 | D13452 | | A | | SM00002 | | | 9 | 162-199 |
| 303B | 16 | | PS | B | 128-0 | 25-29-12 | D13452 | | A | | SM00002 | | | 9 | 275-299 |
| 303R | 16 | | PS | B | 0-0 | 25-29-12 | D13452 | | C | | SM00001 | | | 9 | ALL |
| 303Y | 16 | | PS | B | 0-0 | 25-29-12 | D13452 | | B | | SM00003 | | | 9 | ALL |
| 303Z | | | | B | 0-0 | 25-29-12 | D13452 | | DED | | SM00001 | REF | | 9 | ALL |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|---|----|------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1221 | 286T1221 | ELEC SPOILER CONT PCA 12,W/W DISC TO WING DISC | | | | | | | | | | | | | | | |
| 001 | 20 | | UA | 0-7 | 27-61-13 | SM00001 | | | | | W | | D05481J | 2 | | | ALL |
| 002 | 20 | | UA | 0-7 | 27-61-13 | SM00002 | | | | | W | | D05481J | 4 | | | ALL |
| 003 | 20 | | UA | 0-7 | 27-61-13 | SM00001 | | | | | W | | D05481J | 1 | | | ALL |
| 004 | 20 | | UA | 0-7 | 27-61-13 | SM00002 | | | | | W | | D05481J | 3 | | | ALL |
| 005 | 18 | | UA | 1-5 | 27-61-13 | GD00457 | | | | S.. | N | | D05481J | 10 | | | ALL |
| WBK | 20 | | 7N | 1B | 49-9 | 27-61-13 | D05243J | | | | 2 | | D05481J | 8 | | | ALL |
| WBKZ | | | | 1B | 0-0 | 27-61-13 | GD00433 | | | | S.. | N | GD00457 | S.. | N | | ALL |
| WBN | 20 | | 7N | 1B | 0-0 | 27-61-13 | D05243J | | | | 6 | | D05481J | 6 | | | ALL |
| WBU | 20 | | 7N | 1B | 0-0 | 27-61-13 | D05243J | | | | 3 | | SM00002 | | W | | ALL |
| WOR | 20 | | 7N | 1B | 0-0 | 27-61-13 | D05243J | | | | 5 | | D05481J | 5 | | | ALL |
| WRB | 20 | | 7N | 1B | 0-0 | 27-61-13 | D05243J | | | | 7 | | D05481J | 7 | | | ALL |
| WRD | 20 | | 7N | 1B | 0-0 | 27-61-13 | D05243J | | | | 1 | | SM00001 | | W | | ALL |
| WVI | 20 | | 7N | 1B | 0-0 | 27-61-13 | D05243J | | | | 4 | | D05481J | 9 | | | ALL |
| W1222 | 286T1222 | RIGHT FORWARD EMER LIGHT | | | | | | | | | | | | | | | |
| 002 | 20 | | PA | 30-0 | 33-21-21 | D05124P | | | | | 2 | | D05088P | 2 | | | 050-099, 275-299 |
| 002 | 20 | | PA | 29-0 | 33-21-21 | D05124P | | | | | 2 | | D05088P | 2 | | | 150-199 |
| 003 | 22 | | PA | 30-0 | 21-61-31 | D05124P | | | | | 3 | | D05088P | 3 | | | 050-099, 275-299 |
| 003 | 22 | | PA | 29-0 | 21-61-31 | D05124P | | | | | 3 | | D05088P | 3 | | | 150-199 |
| 004 | 22 | | PA | 30-0 | 21-61-21 | D05124P | | | | | 4 | | D05088P | 4 | | | 050-099, 275-299 |
| 004 | 22 | | PA | 29-0 | 21-61-21 | D05124P | | | | | 4 | | D05088P | 4 | | | 150-199 |
| 005 | 24 | | PK | 30-0 | 33-24-11 | D05124P | | | | | 11 | | D05088P | 11 | | | 050-099, 275-299 |
| 005 | 24 | | PK | 29-0 | 33-24-11 | D05124P | | | | | 11 | | D05088P | 11 | | | 150-199 |
| 006 | 20 | | PA | 29-0 | SPARE | D05124P | | | | | 12 | | D05088P | 12 | | | 150-157 |
| 006 | 20 | | PA | 30-0 | SPARE | D05124P | | | | | 12 | | D05088P | 12 | | | 275-299 |
| 008 | 24 | | PK | 30-0 | 33-24-11 | D05124P | | | | | 13 | | D05088P | 14 | | | 050-099, 275-299 |
| 008 | 24 | | PK | 29-0 | 33-24-11 | D05124P | | | | | 13 | | D05088P | 14 | | | 150-199 |
| 009 | 18 | | PA | 30-0 | 33-51-11 | D05124P | | | | | 14 | DL | D05088P | 21 | DK | | 050-099, 275-299 |
| 009 | 18 | | PA | 29-0 | 33-51-11 | D05124P | | | | | 14 | DL | D05088P | 21 | DK | | 150-199 |
| 010 | 18 | | PA | 30-0 | 33-51-11 | D05124P | | | | | 15 | DL | D05088P | 23 | DK | | 050-099, 275-299 |
| 010 | 18 | | PA | 29-0 | 33-51-11 | D05124P | | | | | 15 | DL | D05088P | 23 | DK | | 150-199 |
| 011 | 22 | | PA | 30-0 | 33-51-11 | D05124P | | | | | 16 | | D05088P | 28 | | | 050-099, 275-299 |
| 011 | 22 | | PA | 29-0 | 33-51-11 | D05124P | | | | | 16 | | D05088P | 28 | | | 150-199 |
| 013 | 22 | | PA | 30-0 | 33-51-11 | D05124P | | | | | 18 | | D05088P | 30 | | | 050-099, 275-299 |
| 013 | 22 | | PA | 29-0 | 33-51-11 | D05124P | | | | | 18 | | D05088P | 30 | | | 150-199 |
| 014 | 20 | | PA | 3-0 | 33-51-11 | D02746 | | | | | 7 | | GD05664 | S.. | E | | 050-099, 150-199 |
| 014 | 20 | | PA | 4-0 | 33-51-11 | D02746 | | | | | 7 | | GD02448 | S.. | E | | 275-299 |
| 015 | 22 | | PA | 2-0 | 33-51-11 | D02746 | | | | | 5 | | D02746 | 6 | | | 050-099 |
| 015 | 22 | | PA | 1-0 | 33-51-11 | D02746 | | | | | 5 | | D02746 | 6 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1222 | 286T1222 | | | RIGHT FORWARD EMER LIGHT (continued) | | | | | | | | | | | |
| 016 | 20 | | PA | | 19-0 | 33-51-11 | D02746 | | | 2 | SM00030 | | | S | 050-099 |
| 016 | 20 | | PA | | 7-0 | 33-51-11 | D02746 | | | 2 | SM00030 | | | S | 150-199 |
| 016 | 20 | | PA | | 22-0 | 33-51-11 | D02746 | | | 2 | D05088P | 24 | | | 275-299 |
| 017 | 22 | | PA | | 19-0 | 33-51-11 | D02746 | | | 4 | SM00028 | | | S | 050-099 |
| 017 | 22 | | PA | | 7-0 | 33-51-11 | D02746 | | | 4 | SM00028 | | | S | 150-199 |
| 017 | 22 | | PA | | 22-0 | 33-51-11 | D02746 | | | 4 | D05088P | 25 | | | 275-299 |
| 018 | 22 | | PA | | 82-0 | 33-51-11 | SM00029 | | S | | SP02506 | | | S | 050-099 |
| 018 | 22 | | PA | | 101-0 | 33-51-11 | SM00029 | | S | | SP02506 | | | S | 150-199 |
| 018 | 22 | | PA | | 118-0 | 33-51-11 | D02746 | | | 3 | SP02506 | | | S | 275-299 |
| 019 | 22 | | PA | | 33-0 | 33-51-11 | D02746 | | | 8 | D05088P | 27 | | | 050-099, 150-199, 275-278 |
| 019 | 22 | | PA | | 22-0 | 33-51-11 | D02746 | | | 8 | D05088P | 27 | | | 280-299 |
| 020 | 20 | | PA | | 3-0 | 33-51-11 | D02746 | | | 1 | GD05666 | D.. | E | | 050-099 |
| 020 | 20 | | PA | | 2-0 | 33-51-11 | D02746 | | | 1 | GD05666 | D.. | E | | 150-199 |
| 020 | 20 | | PA | | 4-0 | 33-51-11 | D02746 | | | 1 | GD02450 | D.. | E | | 275-299 |
| 021 | 20 | | PA | | 26-0 | 33-51-12 | D02746 | | | 16 | L00294 | 1 | C | | 050-099 |
| 021 | 20 | | PA | | 22-0 | 33-51-12 | D02746 | | | 16 | L00294 | 1 | C | | 150-199 |
| 021 | 20 | | PA | | 35-0 | 33-51-12 | D02746 | | | 16 | L00294 | 1 | C | | 275-278 |
| 021 | 20 | | PA | | 35-0 | 33-51-12 | D02746 | | | 16 | ST0631R | REF | * | | 280-299 |
| 022 | 22 | | PA | | 18-0 | 33-51-12 | D02746 | | | 15 | L00293 | 1 | C | | 050-099 |
| 022 | 22 | | PA | | 28-0 | 33-51-12 | D02746 | | | 15 | L00293 | 1 | C | | 150-199, 275-299 |
| 023 | 18 | | PA | | 40-0 | 33-51-12 | D02746 | | DK | 14 | L00299 | 1 | C | | 050-099 |
| 023 | 18 | | PA | | 31-0 | 33-51-12 | D02746 | | DK | 14 | L00776 | 1 | C | | 150-199 |
| 023 | 18 | | PA | | 15-0 | 33-51-12 | D02746 | | DK | 14 | SM00014 | | | S | 275-299 |
| 024 | 18 | | PA | | 47-0 | 33-51-12 | L00291 | | | 1 | D02746 | 13 | DK | | 050-099 |
| 024 | 18 | | PA | | 46-0 | 33-51-12 | D02746 | | DK | 13 | L00291 | 1 | C | | 150-199 |
| 024 | 18 | | PA | | 33-0 | 33-51-12 | D02746 | | DK | 13 | L00291 | 1 | C | | 275-299 |
| 025 | 22 | | PA | | 39-0 | 33-51-12 | D02746 | | | 12 | L00290 | 1 | C | | 150-157 |
| 025 | 18 | | PA | | 39-0 | 33-51-12 | D02746 | | DK | 12 | L00290 | 1 | C | * | 162-199 |
| 025 | 22 | | PA | | 33-0 | 33-51-12 | D02746 | | | 12 | L00290 | 1 | C | | 275-299 |
| 026 | 16 | | PA | | 41-0 | 33-51-12 | D02746 | | FM | 11 | SP03580 | | | S | 150-157 |
| 026 | 18 | | PA | | 41-0 | 33-51-12 | D02746 | | DK | 11 | L00289 | 1 | C | | 162-199 |
| 026 | 18 | | PA | | 32-0 | 33-51-12 | D02746 | | DK | 11 | L00289 | 1 | C | | 275-299 |
| 027 | 20 | | PA | | 48-0 | 33-51-12 | D02746 | | | 10 | L00288 | 1 | C | | 150-199, 275-299 |
| 028 | 18 | | PA | | 29-0 | 33-51-12 | SM00014 | | S | | L00776 | 1 | C | | 275-278 |
| 028 | 18 | | PA | | 29-0 | 33-51-12 | SM00014 | | S | | ST654R | REF | * | | 280-299 |
| 031 | 18 | | PA | | 18-0 | 33-51-12 | L00289 | | | 1 | SP03580 | | | S | 150-157 |
| 032 | 20 | | PA | | 5-0 | 33-51-12 | L00288 | | | 2 | GD01236 | D.. | 2 | | 150-199 |
| 032 | 20 | | PA | | 6-0 | 33-51-12 | L00288 | | | 2 | GD01236 | D.. | 2 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 3

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1222 | 286T1222 | | | RIGHT FORWARD EMER LIGHT (continued) | | | | | | | | | | | | | |
| 033 | 18 | | PA | 18-0 | 33-51-12 | L00289 | | 2 | C | * | | | GD01114 | D.. | 2 | | 150-157 |
| 033 | 18 | | PA | 18-0 | 33-51-12 | L00289 | | 2 | C | | | | GD01114 | D.. | 2 | | 162-199 |
| 033 | 18 | | PA | 19-0 | 33-51-12 | L00289 | | 2 | C | | | | GD01114 | D.. | 2 | | 275-299 |
| 034 | 20 | | PA | 5-0 | 33-51-12 | L00290 | | 2 | C | | | | GD01114 | D.. | 2 | | 150-199 |
| 034 | 20 | | PA | 9-0 | 33-51-12 | L00290 | | 2 | C | | | | GD01114 | D.. | 2 | | 275-299 |
| 035 | 18 | | PA | 16-0 | 33-51-12 | L00291 | | 2 | C | | | | GD01114 | D.. | 2 | | 050-099 |
| 035 | 18 | | PA | 15-0 | 33-51-12 | L00291 | | 2 | C | | | | GD01114 | D.. | 2 | | 150-199 |
| 035 | 18 | | PA | 12-0 | 33-51-12 | L00291 | | 2 | C | | | | GD01114 | D.. | 2 | | 275-299 |
| 036 | 20 | | PA | 16-0 | 33-51-12 | L00292 | | 2 | C | | | | GD01114 | D.. | 2 | | 050-099 |
| 036 | 20 | | PA | 15-0 | 33-51-12 | L00292 | | 2 | C | | | | GD01114 | D.. | 2 | | 150-199 |
| 036 | 20 | | PA | 9-0 | 33-51-12 | L00292 | | 2 | C | | | | GD00938 | D.. | 2 | | 275-299 |
| 037 | 20 | | PA | 7-0 | 33-51-12 | L00293 | | 2 | C | | | | GD02490 | D.. | E | | 050-099, 275-299 |
| 037 | 20 | | PA | 6-0 | 33-51-12 | L00293 | | 2 | C | | | | GD02490 | D.. | E | | 150-199 |
| 038 | 20 | | PA | 7-0 | 33-51-12 | L00294 | | 2 | C | | | | GD02492 | D.. | E | | 050-099, 275-278 |
| 038 | 20 | | PA | 6-0 | 33-51-12 | L00294 | | 2 | C | | | | GD02492 | D.. | E | | 150-199 |
| 038 | 20 | | PA | 7-0 | 33-51-12 | ST0631R | | | | REF | * | | GD02492 | D.. | E | | 280-299 |
| 039 | 16 | | PA | 30-0 | 33-26-21 | D05124P | | 19 | FL | | | | D05088P | 15 | FM | | 050-099, 275-299 |
| 039 | 16 | | PA | 29-0 | 33-26-21 | D05124P | | 19 | FL | | | | D05088P | 15 | FM | | 150-199 |
| 040 | 22 | | PA | 2-0 | 33-51-12 | D02746 | | 20 | | | | | D02746 | 24 | | | 050-099 |
| 040 | 22 | | PA | 1-0 | 33-51-12 | D02746 | | 20 | | | | | D02746 | 24 | | | 150-199, 275-299 |
| 041 | 22 | | PA | 30-0 | 33-26-11 | D05124P | | 20 | | | | | D05088P | 20 | | | 050-099, 275-299 |
| 041 | 22 | | PA | 29-0 | 33-26-11 | D05124P | | 20 | | | | | D05088P | 20 | | | 150-199 |
| 042 | 24 | | PK | 30-0 | 24-51-51 | D05088P | | 13 | | | | | D05124P | 27 | | | 050-099, 275-299 |
| 042 | 24 | | PK | 29-0 | 24-51-51 | D05088P | | 13 | | | | | D05124P | 27 | | | 150-199 |
| 043 | 24 | | PK | 30-0 | 24-51-51 | D05088P | | 18 | | | | | D05124P | 26 | | | 050-099, 275-299 |
| 043 | 24 | | PK | 29-0 | 24-51-51 | D05088P | | 18 | | | | | D05124P | 26 | | | 150-199 |
| 045 | 24 | | PK | 30-0 | 24-51-51 | D05088P | | 16 | | | | | D05124P | 24 | | | 050-099, 275-299 |
| 045 | 24 | | PK | 29-0 | 24-51-51 | D05088P | | 16 | | | | | D05124P | 24 | | | 150-199 |
| 046 | 20 | | PA | 30-0 | 33-26-11 | D05124P | | 28 | | | | | D05088P | 19 | | | 050-099, 275-299 |
| 046 | 20 | | PA | 29-0 | 33-26-11 | D05124P | | 28 | | | | | D05088P | 19 | | | 150-199 |
| 048 | 20 | | PA | 30-0 | 33-41-11 | D05124P | | 22 | | | | | D05088P | 31 | | | 050-099 |
| 048 | 18 | | PA | 29-0 | 33-41-11 | D05124P | | 22 | DL | | | | D05088P | 31 | DK | | 150-199 |
| 048 | 18 | | PA | 30-0 | 33-41-11 | D05124P | | 22 | DL | | | | D05088P | 31 | DK | | 275-299 |
| 049 | 20 | | PA | 30-0 | 33-41-11 | D05124P | | 23 | | | | | D05088P | 32 | | | 050-099 |
| 049 | 18 | | PA | 29-0 | 33-41-11 | D05124P | | 23 | DL | | | | D05088P | 32 | DK | | 150-199 |
| 049 | 18 | | PA | 30-0 | 33-41-11 | D05124P | | 23 | DL | | | | D05088P | 32 | DK | | 275-299 |
| 051 | 20 | | PA | 30-0 | 33-21-11 | D05124P | | 1 | | | | | D05088P | 1 | | | 050-099 |
| 051 | 20 | | PA | 29-0 | 33-21-11 | D05124P | | 40 | | | | | D05088P | 1 | | | 150-199 |
| 053 | 22 | | PA | 32-0 | 33-51-11 | SM00033 | | | S | | | | D05088P | 34 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|---|----|---|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W1222 | 286T1222 | | | RIGHT FORWARD EMER LIGHT (continued) | | | | | | | | | | | | | | | |
| 053 | 22 | | PA | 38-0 | 33-51-11 | SM00033 | | | | S | | | | D05088P | 34 | | | | 150-199 |
| 053 | 22 | | PA | 83-0 | 33-51-11 | D01126 | | | 2 | | | | | D05088P | 34 | | | | 275-299 |
| 054 | 22 | | PA | 32-0 | 33-51-11 | SM00031 | | | | S | | | | D05088P | 35 | | | | 050-099 |
| 054 | 22 | | PA | 38-0 | 33-51-11 | SM00031 | | | | S | | | | D05088P | 35 | | | | 150-199 |
| 054 | 22 | | PA | 83-0 | 33-51-11 | D01126 | | | 4 | | | | | D05088P | 35 | | | | 275-299 |
| 055 | 20 | | PA | 4-0 | 33-51-11 | D01126 | | | 1 | | | | | GD02580 | D.. | | E | | ALL |
| 056 | 22 | | PA | 22-0 | 33-51-11 | SM00032 | | | | S | | | | SP02504 | | | S | | 050-099 |
| 056 | 22 | | PA | 29-0 | 33-51-11 | SM00032 | | | | S | | | | SP02504 | | | S | | 150-199 |
| 056 | 22 | | PA | 74-0 | 33-51-11 | D01126 | | | 3 | | | | | SP02504 | | | S | | 275-299 |
| 057 | 20 | | PA | 4-0 | 33-51-11 | D01126 | | | 7 | | | | | GD02582 | S.. | | E | | ALL |
| 058 | 22 | | PA | 73-0 | 33-51-11 | D01126 | | | 8 | | | | | D05088P | 36 | | | | 050-099 |
| 058 | 22 | | PA | 83-0 | 33-51-11 | D01126 | | | 8 | | | | | D05088P | 36 | | | | 150-199, 275-299 |
| 059 | 22 | | PA | 1-0 | 33-51-11 | D01126 | | | 5 | | | | | D01126 | 6 | | | | ALL |
| 061 | 20 | | PA | 17-0 | 33-51-12 | D01126 | | | 16 | | | | | L00301 | 1 | | C | | 050-099 |
| 061 | 20 | | PA | 21-0 | 33-51-12 | D01126 | | | 16 | | | | | L00302 | 1 | | C | | 150-199, 275-299 |
| 062 | 22 | | PA | 24-0 | 33-51-12 | D01126 | | | 15 | | | | | L00300 | 1 | | C | | 050-099 |
| 062 | 22 | | PA | 24-0 | 33-51-12 | D01126 | | | 15 | | | | | L00301 | 1 | | C | | 150-199 |
| 062 | 22 | | PA | 19-0 | 33-51-12 | D01126 | | | 15 | | | | | L00301 | 1 | | C | | 275-299 |
| 063 | 22 | | PA | 1-0 | 33-51-12 | D01126 | | | 24 | | | | | D01126 | 20 | | | | ALL |
| 065 | 16 | | PA | 26-0 | 33-51-12 | D01126 | | | 12 | FM | | | | L00298 | 1 | | C | | 150-154, 162-199 |
| 065 | 16 | | PA | 26-0 | 33-51-12 | D01126 | | | 12 | FM | | | | ST0932R | REF | * | | * | 155, 157 |
| 065 | 16 | | PA | 31-3 | 33-51-12 | D01126 | | | 12 | FM | | | | L00298 | 1 | | C | | 156 |
| 065 | 16 | | PA | 35-0 | 33-51-12 | D01126 | | | 12 | FM | | | | L00298 | 1 | | C | | 275-276 |
| 065 | 16 | | PA | 28-11 | 33-51-12 | D01126 | | | 12 | FM | | | | L00298 | 1 | | C | | 277-278 |
| 065 | 16 | | PA | 30-0 | 33-51-12 | D01126 | | | 12 | FM | | | | L00298 | 1 | | C | | 280-299 |
| 066 | 20 | | PA | 28-0 | 33-51-12 | D01126 | | | 11 | | | | | L00302 | 1 | | C | | 050-099 |
| 066 | 20 | | PA | 28-0 | 33-51-12 | D01126 | | | 11 | | | | | L00303 | 1 | | C | | 150-199, 275-299 |
| 067 | 20 | | PA | 36-0 | 33-51-12 | D01126 | | | 10 | | | | | L00296 | 1 | | C | | 150-199 |
| 067 | 20 | | PA | 44-0 | 33-51-12 | D01126 | | | 10 | | | | | L00296 | 1 | | C | * | 275-278 |
| 067 | 20 | | PA | 35-0 | 33-51-12 | D01126 | | | 10 | | | | | L00296 | 1 | | C | * | 280-299 |
| 068 | 16 | | PA | 23-0 | 33-51-12 | D01126 | | | 9 | FM | | | | L01050 | 1 | | C | | 050-099 |
| 068 | 18 | | PA | 27-0 | 33-51-12 | D01126 | | | 9 | DK | | | | D06650J | 1 | | DK | | 150-154, 156, 162-199 |
| 068 | 18 | | PA | 1-0 | 33-51-12 | D01126 | | | 9 | DK | | | | SM00063 | | | S | | 155 |
| 068 | 18 | | PA | 2-0 | 33-51-12 | D01126 | | | 9 | DK | | | | SM00063 | | | S | | 157 |
| 068 | 18 | | PA | 32-0 | 33-51-12 | D01126 | | | 9 | DK | | | | L00321 | 1 | | C | * | 275-299 |
| 069 | 20 | | PA | 6-0 | 33-51-12 | L00295 | | | 2 | C | | | | GD03910 | D.. | | E | | 050-099 |
| 072 | 20 | | PA | 10-0 | 33-51-12 | L00296 | | | 2 | C | | | | GD02496 | D.. | | E | | 150-199 |
| 072 | 20 | | PA | 6-0 | 33-51-12 | L00296 | | | 2 | C | | * | | GD02496 | D.. | | E | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1220
Page 5
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1222 | 286T1222 | | | RIGHT FORWARD EMER LIGHT (continued) | | | | | | | | | | | | | |
| 074 | 16 | PA | | 14-0 | 33-51-12 | L00298 | | 2 | C | | | | GD04654 | D.. | E | | 150-154, 162-199, 275-276 |
| 074 | 16 | PA | | 15-0 | 33-51-12 | ST0932R | REF | * | | | | | GD04654 | D.. | E | | 155, 157 |
| 074 | 16 | PA | | 7-2 | 33-51-12 | L00298 | | 2 | C | | | | GD04654 | D.. | E | | 156 |
| 074 | 16 | PA | | 7-9 | 33-51-12 | L00298 | | 2 | C | | | | GD04508 | D.. | E | | 277-278 |
| 074 | 16 | PA | | 13-2 | 33-51-12 | L00298 | | 2 | C | | | | GD04508 | D.. | E | | 280-299 |
| 075 | 20 | PA | | 7-0 | 33-51-12 | L00301 | | 2 | C | | | | GD02506 | D.. | E | | 050-099 |
| 075 | 20 | PA | | 13-0 | 33-51-12 | L00301 | | 2 | C | | | | GD04654 | D.. | E | | 150-154, 156-199 |
| 075 | 20 | PA | | 16-0 | 33-51-12 | L00301 | | 2 | C | | | | GD04654 | D.. | E | | 155 |
| 075 | 20 | PA | | 7-0 | 33-51-12 | L00301 | | 2 | C | | | | GD04918 | D.. | E | | 275-299 |
| 076 | 20 | PA | | 6-0 | 33-51-12 | L00300 | | 2 | C | | | | GD04418 | D.. | E | | 050-099 |
| 076 | 20 | PA | | 6-0 | 33-51-12 | L00300 | | 2 | C | | | | GD04508 | D.. | E | | 150-199 |
| 077 | 20 | PA | | 24-0 | 33-51-12 | L00302 | | 2 | C | | | | GD02504 | D.. | E | | 050-099 |
| 077 | 20 | PA | | 10-0 | 33-51-12 | L00302 | | 2 | C | | | | GD04888 | D.. | E | | 150-199, 275-299 |
| 080 | 20 | PA | | 7-0 | 33-51-12 | L00303 | | 2 | C | | | | GD02508 | D.. | E | | 050-099 |
| 080 | 20 | PA | | 6-0 | 33-51-12 | GD04930 | | D.. | E | | | | L00303 | | 2 | C | 150-199 |
| 080 | 20 | PA | | 7-0 | 33-51-12 | GD04930 | | D.. | E | | | | L00303 | | 2 | C | 275-299 |
| 081 | 22 | PA | | 128-0 | 33-51-11 | D05124P | | 30 | | | | | SP02506 | | S | | 050-099 |
| 081 | 22 | PA | | 143-0 | 33-51-11 | D05124P | | 30 | | | | | SP02506 | | S | | 150-199, 275-299 |
| 082 | 18 | PA | | 44-0 | 33-51-12 | D01126 | | 14 | DK | | | | L00777 | | 1 | C | 150-199 |
| 082 | 18 | PA | | 45-0 | 33-51-12 | D01126 | | 14 | DK | | | | L00777 | | 1 | C | 275-299 |
| 084 | 18 | PA | | 8-0 | 33-51-12 | L00299 | | 2 | C | | | | GD01114 | D.. | 2 | | 050-099 |
| 084 | 18 | PA | | 15-0 | 33-51-12 | L00289 | | 1 | C | * | | | L00299 | | 1 | C | 150-157 |
| 084 | 18 | PA | | 4-0 | 33-51-12 | L00290 | | 1 | C | * | | | L00299 | | 1 | C | 162-199 |
| 087 | 22 | PA | | 30-0 | 25-65-11 | D05124P | | 31 | | | | | D05088P | | 26 | | 050-099, 275-299 |
| 087 | 22 | PA | | 29-0 | 25-65-11 | D05124P | | 31 | | | | | D05088P | | 26 | | 150-199 |
| 088 | 22 | PA | | 30-0 | 25-65-12 | D05124P | | 32 | | | | | D05088P | | 29 | | 050-099, 275-299 |
| 088 | 22 | PA | | 29-0 | 25-65-12 | D05124P | | 32 | | | | | D05088P | | 29 | | 150-199 |
| 089 | 22 | PA | | 30-0 | 25-65-12 | D05124P | | 33 | | | | | D05088P | | 37 | | 050-099, 275-299 |
| 089 | 22 | PA | | 29-0 | 25-65-12 | D05124P | | 33 | | | | | D05088P | | 37 | | 150-199 |
| 090 | 22 | PA | | 30-0 | SPARE | D05124P | | 34 | | | | | D05088P | | 38 | | 050-099, 275-299 |
| 090 | 22 | PA | | 29-0 | SPARE | D05124P | | 34 | | | | | D05088P | | 38 | | 150-199 |
| 091 | 22 | PA | | 30-0 | 25-65-12 | D05124P | | 35 | | | | | D05088P | | 39 | | 050-099, 275-299 |
| 091 | 22 | PA | | 29-0 | 25-65-12 | D05124P | | 35 | | | | | D05088P | | 39 | | 150-199 |
| 092 | 22 | PA | | 29-0 | SPARE | D05124P | | 36 | | | | | D05088P | | 40 | | 150-157 |
| 092 | 22 | PA | | 30-0 | SPARE | D05124P | | 36 | | | | | D05088P | | 40 | | 275-299 |
| 096 | 22 | PA | | 30-0 | 21-61-41 | D05124P | | 46 | | | | | D05088P | | 46 | | 050-099 |
| 096 | 22 | PA | | 29-0 | 21-61-41 | D05124P | | 46 | | | | | D05088P | | 46 | | 150-199, 275-299 |
| 097 | 18 | PA | | 7-0 | 33-51-12 | GD04970 | | D.. | E | | | | L00776 | | 2 | C | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1222 | 286T1222 | | | RIGHT FORWARD EMER LIGHT (continued) | | | | | | | | | | | | |
| 097 | 18 | PA | | 7-0 | 33-51-12 | GD04970 | D.. | E | | ST654R | REF | * | | 280-299 | | |
| 098 | 18 | PA | | 7-0 | 33-51-12 | GD04978 | D.. | E | | L00777 | 2 | C | | 150-199, 275-299 | | |
| 099 | 18 | PA | | 5-0 | 33-51-12 | GD01950 | D.. | 2 | | D06650J | 2 | DK | | 150-199 | | |
| 099 | 18 | PA | | 22-0 | 33-51-12 | GD02544 | D.. | 2 | | L00321 | 2 | C | * | 275-278 | | |
| 099 | 18 | PA | | 7-0 | 33-51-12 | GD02544 | D.. | 2 | | L00321 | 2 | C | * | 280-299 | | |
| 105 | 20 | PA | | 2-0 | 33-51-16 | D02746 | | 9 | | D11688 | = 1 | | | 275-299 | | |
| 106 | 20 | PA | | 4-0 | 33-51-16 | D11690 | | = 1 | | GD02450 | D.. | E | | 275-299 | | |
| 109 | 20 | PA | | 4-0 | 33-51-16 | D11698 | | = 1 | | GD02580 | D.. | E | | 275-299 | | |
| 110 | 22 | PA | | 7-0 | 33-51-12 | L00292 | | 1 | C | SM00014 | | S | | 275-278 | | |
| 110 | 22 | PA | | 11-0 | 33-51-12 | L00292 | | 1 | C | SM00014 | | S | | 280-299 | | |
| 117 | 20 | PA | | 47-0 | 33-51-12 | D02746 | | 9 | | L00292 | 1 | C | | 050-099 | | |
| 117 | 20 | PA | | 47-0 | 33-51-12 | D02746 | | 9 | DK | L00292 | 1 | C | | 150-199 | | |
| 118 | 20 | PA | | 31-0 | 33-51-12 | D01126 | | 13 | DK | L00300 | 1 | C | | 150-199 | | |
| 118 | 20 | PA | | 2-0 | 33-51-16 | D01126 | | 13 | | D11696 | = 1 | | | 275-299 | | |
| 171 | 16 | PA | | 25-0 | 33-51-12 | L01050 | | 2 | C | GD02496 | D.. | E | | 050-099 | | |
| 173 | 22 | PA | | 30-0 | 30-46-11 | D05124P | | 17 | | D05088P | 45 | | | 050-099, 275-299 | | |
| 173 | 22 | PA | | 29-0 | 30-46-11 | D05124P | | 17 | | D05088P | 45 | | | 150-199 | | |
| 174 | 22 | PK | | 15-0 | 30-46-11 | D05088P | | 53 | | D06606P | 1 | | | 050-099 | | |
| 174 | 22 | PA | | 15-0 | 30-46-11 | D05088P | | 53 | | D06606P | 1 | | | 150-199, 275-278 | | |
| 174 | 22 | PA | | 16-0 | 30-46-11 | D05088P | | 53 | | D06606P | 1 | | | 280-299 | | |
| 175 | 20 | PA | | 12-0 | 30-46-11 | D06606P | | 2 | | GD01114 | D.. | 2 | | ALL | | |
| 176 | 20 | PA | | 12-0 | 30-46-11 | D06606P | | 3 | | GD01114 | S.. | 2 | | ALL | | |
| 179 | 16 | PA | | 21-0 | 33-51-12 | L00298 | | 1 | C | ST0932R | REF | * | * | 155, 157 | | |
| 180 | 16 | PA | | 6-8 | 33-51-12 | L00298 | | 2 | C | GD04508 | D.. | E | | 155, 157 | | |
| 183 | 18 | PA | | 32-0 | 33-51-12 | L00321 | | 1 | C | SM00063 | | S | | 155, 157 | | |
| 183 | 18 | PA | | 3-0 | 33-51-12 | L00655 | | 1 | C | L00321 | 1 | C | * | 275-299 | | |
| 184 | 18 | PA | | 17-0 | 33-51-12 | L00321 | | 2 | C | GD02544 | D.. | 2 | | 155, 157 | | |
| 184 | 18 | PA | | 3-0 | 33-51-12 | L00655 | | 2 | C | L00321 | 2 | C | * | 275-299 | | |
| 194 | 20 | PA | | 35-0 | 33-51-14 | D13216 | | D | | SM00047 | | S | | 050-099 | | |
| 194 | 20 | PA | | 49-0 | 33-51-14 | D13216 | | D | | SM00047 | | S | | 150-199 | | |
| 195 | 20 | PA | | 35-0 | 33-51-14 | D13216 | | C | | SM00048 | | S | | 050-099 | | |
| 195 | 20 | PA | | 49-0 | 33-51-14 | D13216 | | C | | SM00048 | | S | | 150-199 | | |
| 196 | 20 | PA | | 35-0 | 33-51-14 | D13216 | | B | | SM00039 | | S | | 050-099 | | |
| 196 | 20 | PA | | 49-0 | 33-51-14 | D13216 | | B | | SM00039 | | S | | 150-199 | | |
| 197 | 20 | PA | | 35-0 | 33-51-14 | D13216 | | A | | SM00038 | | S | | 050-099 | | |
| 197 | 20 | PA | | 49-0 | 33-51-14 | D13216 | | A | | SM00038 | | S | | 150-199 | | |
| 198 | 20 | PA | | 34-0 | 33-51-14 | D13218 | | D | | SM00047 | | S | | 050-099 | | |
| 198 | 20 | PA | | 56-0 | 33-51-14 | D13218 | | D | | SM00047 | | S | | 150-199 | | |
| 199 | 20 | PA | | 34-0 | 33-51-14 | D13218 | | C | | SM00048 | | S | | 050-099 | | |

WIRE LIST

D280T132

91-21-11
Section W1220
Page 7
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1222 | 286T1222 | | | RIGHT FORWARD EMER LIGHT (continued) | | | | | | | | | | | | | |
| 199 | 20 | | PA | 56-0 | 33-51-14 | D13218 | | C | | | | | SM00048 | | S | | 150-199 |
| 201B | 20 | | PB A | 30-0 | 21-65-11 | D05124P | | 5 | | | | | D05088P | 5 | | | 050-099, 275-299 |
| 201B | 20 | | PB A | 29-0 | 21-65-11 | D05124P | | 5 | | | | | D05088P | 5 | | | 150-199 |
| 201R | 20 | | PB A | 0-0 | 21-65-11 | D05124P | | 6 | | | | | D05088P | 6 | | | ALL |
| 202B | 20 | | PB B | 30-0 | 21-65-11 | D05124P | | 7 | | | | | D05088P | 7 | | | 050-099, 275-299 |
| 202B | 20 | | PB B | 29-0 | 21-65-11 | D05124P | | 7 | | | | | D05088P | 7 | | | 150-199 |
| 202R | 20 | | PB B | 0-0 | 21-65-11 | D05124P | | 8 | | | | | D05088P | 8 | | | ALL |
| 203B | 20 | | PB C | 30-0 | 21-65-11 | D05124P | | 9 | | | | | D05088P | 9 | | | 050-099, 275-299 |
| 203B | 20 | | PB C | 29-0 | 21-65-11 | D05124P | | 9 | | | | | D05088P | 9 | | | 150-199 |
| 203R | 20 | | PB C | 0-0 | 21-65-11 | D05124P | | 10 | | | | | D05088P | 10 | | | ALL |
| 204B | 20 | | PB D | 30-0 | 21-65-11 | D05124P | | 49 | | | | | D05088P | 49 | | | 050-099, 275-299 |
| 204B | 20 | | PB D | 29-0 | 21-65-11 | D05124P | | 49 | | | | | D05088P | 49 | | | 150-199 |
| 204R | 20 | | PB D | 0-0 | 21-65-11 | D05124P | | 50 | | | | | D05088P | 50 | | | ALL |
| 205B | 20 | | PB E | 30-0 | 21-65-11 | D05124P | | 47 | | | | | D05088P | 47 | | | 050-099, 275-299 |
| 205B | 20 | | PB E | 29-0 | 21-65-11 | D05124P | | 47 | | | | | D05088P | 47 | | | 150-199 |
| 205R | 20 | | PB E | 0-0 | 21-65-11 | D05124P | | 48 | | | | | D05088P | 48 | | | ALL |
| 218B | 22 | | PR IR | 30-0 | 21-66-21 | D05088P | | 42 | | | | | D05124P | 44 | | | 050-099 |
| 218B | 22 | | PR IR | 29-0 | 21-66-21 | D05124P | | 44 | | | | | D05088P | 42 | | | 162-199 |
| 218R | 22 | | PR IR | 0-0 | 21-66-21 | D05088P | | 41 | | | | | D05124P | 43 | | | 050-099 |
| 218R | 22 | | PR IR | 0-0 | 21-66-21 | D05124P | | 43 | | | | | D05088P | 41 | | | 162-199 |
| 218Z | | | IR | 0-0 | 21-66-21 | D05088P | | 40 | | | | | D05124P | 42 | | | 050-099 |
| 218Z | | | IR | 0-0 | 21-66-21 | D05124P | | 42 | | | | | D05088P | 40 | | | 162-199 |
| 506 | 18 | | PA | 15-0 | 33-51-12 | L00289 | | 2 | C | | * | | L00299 | 2 | C | | 150-157 |
| 506 | 18 | | PA | 4-0 | 33-51-12 | GD04192 | | D.. | 2 | | | | L00299 | 2 | C | | 162-199 |
| 511 | 20 | | PA | 33-0 | 33-51-12 | D01126 | | 10 | | | | | L00303 | 1 | C | | 050-099 |
| 515 | 20 | | PA | 34-0 | 33-51-14 | D13218 | | B | | | | | SM00039 | | S | | 050-099 |
| 515 | 20 | | PA | 56-0 | 33-51-14 | D13218 | | B | | | | | SM00039 | | S | | 150-199 |
| 516 | 20 | | PA | 34-0 | 33-51-14 | D13218 | | A | | | | | SM00038 | | S | | 050-099 |
| 516 | 20 | | PA | 56-0 | 33-51-14 | D13218 | | A | | | | | SM00038 | | S | | 150-199 |
| 517 | 20 | | PA | 32-0 | 33-51-12 | D02746 | | 12 | | | | | L00295 | 1 | C | | 050-099 |
| 544 | 18 | | PA | 28-0 | 33-51-12 | D06650J | | 1 | DK | | | | SM00063 | | S | | 155, 157 |
| 601 | 20 | | PA | 19-0 | 33-51-16 | D13242 | | C | | | | | SM00057 | | S | | 050-099 |
| 601 | 20 | | PA | 3-0 | 33-51-16 | D13242 | | C | | | | | D13232 | A | | | 150-199 |
| 602 | 20 | | PA | 19-0 | 33-51-16 | D13242 | | B | | | | | SM00058 | | S | | 050-099 |
| 602 | 20 | | PA | 3-0 | 33-51-16 | D13242 | | B | | | | | D13232 | B | | | 150-199 |
| 603 | 20 | | PA | 19-0 | 33-51-16 | D13242 | | F | | | | | SM00059 | | S | | 050-099 |
| 603 | 20 | | PA | 3-0 | 33-51-16 | D13242 | | F | | | | | D13232 | C | | | 150-199 |
| 604 | 20 | | PA | 19-0 | 33-51-16 | D13242 | | E | | | | | SM00060 | | S | | 050-099 |
| 604 | 20 | | PA | 3-0 | 33-51-16 | D13242 | | E | | | | | D13232 | D | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1222 | 286T1222 | | | RIGHT FORWARD EMER LIGHT (continued) | | | | | | | | | | | |
| 605 | 20 | | PA | | 21-0 | 33-51-16 | D13242 | | | | GD03910 | D.. | E | | 050-099 |
| 605 | 20 | | PA | | 4-0 | 33-51-16 | D13242 | | | | GD05564 | D.. | E | | 150-199 |
| 606 | 22 | | PA | | 19-0 | 33-51-16 | D13242 | | | | SM00031 | | S | | 050-099 |
| 606 | 22 | | PA | | 5-0 | 33-51-16 | D13242 | | | | SM00031 | | S | | 150-199 |
| 607 | 22 | | PA | | 19-0 | 33-51-16 | D13242 | | | | SM00032 | | S | | 050-099 |
| 607 | 22 | | PA | | 5-0 | 33-51-16 | D13242 | | | | SM00032 | | S | | 150-199 |
| 608 | 22 | | PA | | 19-0 | 33-51-16 | D13242 | | | | SM00033 | | S | | 050-099 |
| 608 | 22 | | PA | | 5-0 | 33-51-16 | D13242 | | | | SM00033 | | S | | 150-199 |
| 610 | 20 | | PA | | 22-0 | 33-51-16 | D13238 | | | | SM00038 | | S | | 050-099 |
| 610 | 20 | | PA | | 7-0 | 33-51-16 | D13238 | | | | SM00038 | | S | | 150-199 |
| 611 | 20 | | PA | | 22-0 | 33-51-16 | D13238 | | | | SM00039 | | S | | 050-099 |
| 611 | 20 | | PA | | 7-0 | 33-51-16 | D13238 | | | | SM00039 | | S | | 150-199 |
| 612 | 20 | | PA | | 22-0 | 33-51-16 | D13238 | | | | SM00048 | | S | | 050-099 |
| 612 | 20 | | PA | | 9-0 | 33-51-16 | D13238 | | | | SM00048 | | S | | 150-199 |
| 613 | 20 | | PA | | 22-0 | 33-51-16 | D13238 | | | | SM00047 | | S | | 050-099 |
| 613 | 20 | | PA | | 9-0 | 33-51-16 | D13238 | | | | SM00047 | | S | | 150-199 |
| 614 | 20 | | PA | | 3-0 | 33-51-16 | D13238 | | | | GD05666 | D.. | E | | 050-099, 150-199 |
| 615 | 22 | | PA | | 19-0 | 33-51-16 | D13238 | | | | SM00028 | | S | | 050-099 |
| 615 | 22 | | PA | | 7-0 | 33-51-16 | D13238 | | | | SM00028 | | S | | 150-199 |
| 616 | 22 | | PA | | 13-0 | 33-51-16 | D13238 | | | | SM00029 | | S | | 050-099 |
| 616 | 22 | | PA | | 7-0 | 33-51-16 | D13238 | | | | SM00029 | | S | | 150-199 |
| 617 | 20 | | PA | | 19-0 | 33-51-16 | D13238 | | | | SM00030 | | S | | 050-099 |
| 617 | 20 | | PA | | 7-0 | 33-51-16 | D13238 | | | | SM00030 | | S | | 150-199 |
| 618 | 20 | | PA | | 4-0 | 33-51-16 | D13240 | | | | D13230 | A | | | 050-099, 150-199 |
| 619 | 20 | | PA | | 4-0 | 33-51-16 | D13240 | | | | D13230 | B | | | 050-099, 150-199 |
| 620 | 20 | | PA | | 4-0 | 33-51-16 | D13240 | | | | D13230 | C | | | 050-099, 150-199 |
| 621 | 20 | | PA | | 4-0 | 33-51-16 | D13240 | | | | D13230 | D | | | 050-099, 150-199 |
| 622 | 20 | | PA | | 4-0 | 33-51-16 | D13240 | | | | GD02580 | D.. | E | | 050-099, 150-199 |
| 623 | 22 | | PA | | 4-0 | 33-51-16 | D13240 | | | | SM00035 | | S | | 050-099 |
| 623 | 22 | | PA | | 5-0 | 33-51-16 | D13240 | | | | SM00035 | | S | | 150-199 |
| 624 | 22 | | PA | | 4-0 | 33-51-16 | D13240 | | | | SM00036 | | S | | 050-099 |
| 624 | 22 | | PA | | 5-0 | 33-51-16 | D13240 | | | | SM00036 | | S | | 150-199 |
| 625 | 22 | | PA | | 4-0 | 33-51-16 | D13240 | | | | SM00037 | | S | | 050-099 |
| 625 | 22 | | PA | | 5-0 | 33-51-16 | D13240 | | | | SM00037 | | S | | 150-199 |
| 638 | 22 | | PA | | 42-0 | 33-51-11 | SM00033 | | | S | SM00037 | | S | | 050-099 |
| 638 | 22 | | PA | | 59-0 | 33-51-11 | SM00037 | | | S | SM00033 | | S | | 150-199 |
| 639 | 22 | | PA | | 42-0 | 33-51-11 | SM00035 | | | S | SM00031 | | S | | 050-099 |
| 639 | 22 | | PA | | 59-0 | 33-51-11 | SM00035 | | | S | SM00031 | | S | | 150-199 |
| 640 | 20 | | PA | | 16-0 | 33-51-11 | D05088P | | 24 | | SM00030 | | S | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W1220
Page 9
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1222 | 286T1222 | | | RIGHT FORWARD EMER LIGHT (continued) | | | | | | | | | | | | | |
| 640 | 20 | | PA | 28-0 | 33-51-11 | D05088P | | 24 | | | | | SM00030 | | S | | 150-199 |
| 641 | 22 | | PA | 16-0 | 33-51-11 | D05088P | | 25 | | | | | SM00028 | | S | | 050-099 |
| 641 | 22 | | PA | 28-0 | 33-51-11 | D05088P | | 25 | | | | | SM00028 | | S | | 150-199 |
| 642 | 22 | | PA | 13-0 | 33-51-11 | SM00029 | | | S | | | | D02746 | 3 | | | 050-099 |
| 642 | 22 | | PA | 7-0 | 33-51-11 | D02746 | | 3 | | | | | SM00029 | | S | | 150-162, 164-199 |
| 642 | 22 | | PA | 8-0 | 33-51-11 | D02746 | | 3 | | | | | SM00029 | | S | | 163 |
| 643 | 22 | | PA | 42-0 | 33-51-11 | SM00036 | | | S | | | | SM00032 | | S | | 050-099 |
| 643 | 22 | | PA | 59-0 | 33-51-11 | SM00036 | | | S | | | | SM00032 | | S | | 150-199 |
| 647 | 22 | | PA | 3-0 | 33-51-11 | D01126 | | 2 | | | | | SM00037 | | S | | 050-099 |
| 647 | 22 | | PA | 4-0 | 33-51-11 | SM00037 | | | S | | | | D01126 | 2 | | | 150-199 |
| 648 | 22 | | PA | 3-0 | 33-51-11 | D01126 | | 4 | | | | | SM00035 | | S | | 050-099 |
| 648 | 22 | | PA | 4-0 | 33-51-11 | SM00035 | | | S | | | | D01126 | 4 | | | 150-199 |
| 649 | 22 | | PA | 3-0 | 33-51-11 | D01126 | | 3 | | | | | SM00036 | | S | | 050-099 |
| 649 | 22 | | PA | 4-0 | 33-51-11 | SM00036 | | | S | | | | D01126 | 3 | | | 150-199 |
| 651 | 20 | | PA | 22-0 | 33-51-16 | D13228 | | | B | | | | SM00039 | | S | | 050-099 |
| 651 | 20 | | PA | 7-0 | 33-51-16 | D13228 | | | B | | | | SM00039 | | S | | 150-199 |
| 652 | 20 | | PA | 22-0 | 33-51-16 | D13228 | | | A | | | | SM00038 | | S | | 050-099 |
| 652 | 20 | | PA | 7-0 | 33-51-16 | D13228 | | | A | | | | SM00038 | | S | | 150-199 |
| 653 | 20 | | PA | 20-0 | 33-51-16 | SM00038 | | | S | | | | SM00041 | | S | | 050-099 |
| 653 | 20 | | PA | 33-0 | 33-51-16 | SM00041 | | | S | | | | SM00038 | | S | | 150-199 |
| 654 | 20 | | PA | 20-0 | 33-51-16 | SM00039 | | | S | | | | SM00040 | | S | | 050-099 |
| 654 | 20 | | PA | 33-0 | 33-51-16 | SM00040 | | | S | | | | SM00039 | | S | | 150-199 |
| 655 | 20 | | PA | 13-0 | 33-51-16 | SM00040 | | | S | | | | D13510 | B | | | 150-199 |
| 656 | 20 | | PA | 13-0 | 33-51-16 | SM00041 | | | S | | | | D13510 | A | | | 150-199 |
| 657 | 20 | | PA | 9-0 | 33-51-16 | D13512 | | | B | | | | SM00040 | | S | | 050-099 |
| 657 | 20 | | PA | 8-0 | 33-51-16 | SM00040 | | | S | | | | D13512 | B | | | 150-199 |
| 658 | 20 | | PA | 9-0 | 33-51-16 | D13512 | | | A | | | | SM00041 | | S | | 050-099 |
| 658 | 20 | | PA | 8-0 | 33-51-16 | SM00041 | | | S | | | | D13512 | A | | | 150-199 |
| 659 | 20 | | PA | 4-0 | 33-51-16 | SM00040 | | | S | | | | SM00042 | | S | | 050-099 |
| 659 | 20 | | PA | 3-0 | 33-51-16 | SM00040 | | | S | | | | SM00042 | | S | | 150-199 |
| 660 | 20 | | PA | 4-0 | 33-51-16 | SM00041 | | | S | | | | SM00043 | | S | | 050-099 |
| 660 | 20 | | PA | 3-0 | 33-51-16 | SM00041 | | | S | | | | SM00043 | | S | | 150-199 |
| 661 | 20 | | PA | 7-0 | 33-51-16 | D13514 | | | B | | | | SM00042 | | S | | 050-099 |
| 661 | 20 | | PA | 6-0 | 33-51-16 | D13514 | | | B | | | | SM00042 | | S | | 150-199 |
| 662 | 20 | | PA | 7-0 | 33-51-16 | D13514 | | | A | | | | SM00043 | | S | | 050-099 |
| 662 | 20 | | PA | 6-0 | 33-51-16 | D13514 | | | A | | | | SM00043 | | S | | 150-199 |
| 663 | 20 | | PA | 7-0 | 33-51-16 | D13516 | | | B | | | | SM00042 | | S | | 050-099, 150-199 |
| 664 | 20 | | PA | 7-0 | 33-51-16 | D13516 | | | A | | | | SM00043 | | S | | 050-099, 150-199 |
| 665 | 20 | | PA | 13-0 | 33-51-16 | D13518 | | | B | | | | SM00042 | | S | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1222 | 286T1222 | | | RIGHT FORWARD EMER LIGHT (continued) | | | | | | | | | | | |
| 666 | 20 | | PA | | 13-0 | 33-51-16 | D13518 | | A | | | | | | 050-099, 150-199 |
| 669 | 20 | | PA | | 22-0 | 33-51-12 | L01050 | 2 | C | | | | | * | 275-299 |
| 675 | 20 | | PA | | 22-0 | 33-51-12 | L00296 | 1 | C | * | | | | | 275-299 |
| 676 | 22 | | PA | | 30-0 | 33-22-33 | D05124P | 41 | | | | | | | 050-099 |
| 676 | 22 | | PA | | 29-0 | 33-22-33 | D05124P | 41 | | | | | | | 162-199 |
| 678 | 20 | | PA | | 22-0 | 33-51-16 | D13228 | | D | | | | | S | 050-099 |
| 678 | 20 | | PA | | 9-0 | 33-51-16 | SM00047 | | | S | | | D | | 150-199 |
| 679 | 20 | | PA | | 22-0 | 33-51-16 | D13228 | | C | | | | | S | 050-099 |
| 679 | 20 | | PA | | 9-0 | 33-51-16 | SM00048 | | | S | | | C | | 150-199 |
| 680 | 20 | | PA | | 20-0 | 33-51-16 | SM00047 | | | S | | | | S | 050-099 |
| 680 | 20 | | PA | | 45-0 | 33-51-16 | SM00047 | | | S | | | | S | 150-199 |
| 681 | 20 | | PA | | 20-0 | 33-51-16 | SM00048 | | | S | | | | S | 050-099 |
| 681 | 20 | | PA | | 45-0 | 33-51-16 | SM00048 | | | S | | | | S | 150-199 |
| 682 | 20 | | PA | | 12-0 | 33-51-16 | SM00049 | | | S | | | D | | 150-199 |
| 683 | 20 | | PA | | 45-0 | 33-51-16 | SM00050 | | | S | | | C | | 150-199 |
| 684 | 20 | | PA | | 9-0 | 33-51-16 | D13512 | | D | | | | | S | 050-099 |
| 684 | 20 | | PA | | 9-0 | 33-51-16 | SM00049 | | | S | | | D | | 150-199 |
| 685 | 20 | | PA | | 9-0 | 33-51-16 | D13512 | | C | | | | | S | 050-099 |
| 685 | 20 | | PA | | 9-0 | 33-51-16 | SM00050 | | | S | | | C | | 150-199 |
| 686 | 20 | | PA | | 4-0 | 33-51-16 | SM00049 | | | S | | | | S | 050-099, 150-199 |
| 687 | 20 | | PA | | 4-0 | 33-51-16 | SM00050 | | | S | | | | S | 050-099, 150-199 |
| 688 | 20 | | PA | | 13-0 | 33-51-16 | D13518 | | D | | | | | S | 050-099 |
| 688 | 20 | | PA | | 13-0 | 33-51-16 | SM00051 | | | S | | | D | | 150-199 |
| 689 | 20 | | PA | | 13-0 | 33-51-16 | D13518 | | C | | | | | S | 050-099 |
| 689 | 20 | | PA | | 13-0 | 33-51-16 | SM00052 | | | S | | | C | | 150-199 |
| 690 | 20 | | PA | | 7-0 | 33-51-16 | D13516 | | D | | | | | S | 050-099 |
| 690 | 20 | | PA | | 7-0 | 33-51-16 | SM00051 | | | S | | | D | | 150-199 |
| 691 | 20 | | PA | | 7-0 | 33-51-16 | D13516 | | C | | | | | S | 050-099 |
| 691 | 20 | | PA | | 7-0 | 33-51-16 | SM00052 | | | S | | | C | | 150-199 |
| 692 | 20 | | PA | | 7-0 | 33-51-16 | D13514 | | D | | | | | S | 050-099 |
| 692 | 20 | | PA | | 7-0 | 33-51-16 | SM00051 | | | S | | | D | | 150-199 |
| 693 | 20 | | PA | | 7-0 | 33-51-16 | D13514 | | C | | | | | S | 050-099 |
| 693 | 20 | | PA | | 7-0 | 33-51-16 | SM00052 | | | S | | | C | | 150-199 |
| 700 | 20 | | PA | | 13-0 | 33-51-16 | D13232 | | D | | | | | S | 050-099 |
| 701 | 20 | | PA | | 13-0 | 33-51-16 | D13232 | | C | | | | | S | 050-099 |
| 702 | 20 | | PA | | 13-0 | 33-51-16 | D13232 | | B | | | | | S | 050-099 |
| 703 | 20 | | PA | | 13-0 | 33-51-16 | D13232 | | A | | | | | S | 050-099 |
| 704 | 20 | | PA | | 46-0 | 33-51-14 | D13222 | | A | | | | | S | 050-099 |
| 705 | 20 | | PA | | 46-0 | 33-51-14 | D13222 | | B | | | | | S | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 11

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1222 | 286T1222 | | | RIGHT FORWARD EMER LIGHT (continued) | | | | | | | | | | | | | |
| 706 | 20 | | PA | 46-0 | 33-51-14 | D13222 | | C | | | | | SM00059 | | S | | 050-099 |
| 707 | 20 | | PA | 46-0 | 33-51-14 | D13222 | | D | | | | | SM00060 | | S | | 050-099 |
| 708 | 20 | | PA | 14-0 | 33-51-16 | D12254 | | A | | | | | SM00043 | | S | | 050-099 |
| 709 | 20 | | PA | 14-0 | 33-51-16 | D12254 | | B | | | | | SM00042 | | S | | 050-099 |
| 710 | 20 | | PA | 14-0 | 33-51-16 | D12254 | | C | | | | | SM00052 | | S | | 050-099 |
| 711 | 20 | | PA | 14-0 | 33-51-16 | D12254 | | D | | | | | SM00051 | | S | | 050-099 |
| 712 | 22 | | PA | 30-0 | 21-66-21 | D05088P | | 12 | | | | | D05124P | 37 | | | 050-099 |
| 712 | 22 | | PA | 29-0 | 21-66-21 | D05088P | | 12 | | | | | D05124P | 37 | | | 162-199 |
| 713 | 22 | | PA | 30-0 | 21-66-21 | D05088P | | 17 | | | | | D05124P | 29 | | | 050-099 |
| 713 | 22 | | PA | 29-0 | 21-66-21 | D05088P | | 17 | | | | | D05124P | 29 | | | 162-199 |
| 714 | 22 | | PA | 30-0 | 21-66-21 | D05088P | | 22 | | | | | D05124P | 36 | | | 050-099 |
| 714 | 22 | | PA | 29-0 | 21-66-21 | D05124P | | 36 | | | | | D05088P | 22 | | | 162-199 |
| 715 | 22 | | PA | 30-0 | 21-66-21 | D05088P | | 33 | | | | | D05124P | 21 | | | 050-099 |
| 715 | 22 | | PA | 29-0 | 21-66-21 | D05124P | | 21 | | | | | D05088P | 33 | | | 162-199 |
| 717 | 22 | | PA | 30-0 | 21-66-21 | D05088P | | 43 | | | | | D05124P | 38 | | | 050-099 |
| 717 | 22 | | PA | 29-0 | 21-66-21 | D05124P | | 38 | | | | | D05088P | 43 | | | 162-199 |
| 718 | 22 | | PA | 30-0 | 21-66-21 | D05088P | | 44 | | | | | D05124P | 39 | | | 050-099 |
| 718 | 22 | | PA | 29-0 | 21-66-21 | D05124P | | 39 | | | | | D05088P | 44 | | | 162-199 |
| 719 | 22 | | PA | 30-0 | 21-66-41 | D05088P | | 54 | | | | | D05124P | 12 | | | 050-099 |
| 719 | 22 | | PA | 29-0 | 21-66-41 | D05290P | | 13 | | | | | D05088P | 54 | | | 150, 152-157 |
| 719 | 22 | | PA | 29-0 | 21-66-41 | D05124P | | 12 | | | | | D05088P | 54 | | | 162-199 |
| 720 | 22 | | PA | 30-0 | 21-66-41 | D05088P | | 52 | | | | | D05124P | 45 | | | 050-099 |
| 720 | 22 | | PA | 29-0 | 21-66-41 | D05496J | | 15 | | | | | D05088P | 52 | | | 150, 152-157 |
| 720 | 22 | | PA | 29-0 | 21-66-41 | D05124P | | 45 | | | | | D05088P | 52 | | | 162-199 |
| 814 | 20 | | PA | 30-0 | 33-26-11 | D05124P | | 25 | | | | | D05088P | 51 | | | 050-099 |
| 814 | 20 | | PA | 29-0 | 33-26-11 | D05124P | | 25 | | | | | D05088P | 51 | | | 150-199 |
| 814 | 20 | | PA | 30-0 | SPARE | D05124P | | 51 | | | | | D05088P | 51 | | | 275-299 |
| W1224 | 286T1224 | | | FORWARD ENTRY DOOR CONTROL,L FWD ATTEND. PNL | | | | | | | | | | | | | |
| 001 | 22 | | PA | 14-0 | 52-11-11 | D04290P | | 2 | | | | | D01466 | 2 | | | ALL |
| 002 | 22 | | PA | 14-0 | 52-11-11 | D04290P | | 30 | | | | | D01466 | 1 | | | ALL |
| 003 | 22 | | PA | 14-0 | 52-11-11 | D04290P | | 31 | | | | | D01466 | 3 | | | ALL |
| 004 | 20 | | PA | 5-5 | 52-11-11 | GD00760 | | A.. | 2 | | | | D01466 | 4 | | | 050-099, 275-299 |
| 004 | 20 | | PA | 7-0 | 52-11-11 | GD00760 | | A.. | 2 | | | | D01466 | 4 | | | 150-199 |
| 005 | 20 | | PA | 5-5 | 52-11-11 | D01466 | | 5 | | | | | GD00760 | S.. | 2 | | 050-099, 275-299 |
| 005 | 20 | | PA | 7-0 | 52-11-11 | D01466 | | 5 | | | | | GD00760 | S.. | 2 | | 150-199 |
| 006 | 22 | | PA | 31-0 | 52-11-12 | D04290P | | 32 | | | | | D01646 | 26 | | | 050-099 |
| 006 | 22 | | PA | 30-0 | 52-11-12 | D04290P | | 32 | | | | | D01646 | 26 | | | 150-199, 275-299 |
| 007 | 22 | | PA | 20-0 | 52-11-12 | D04290P | | 33 | | | | | SM00001 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1224 | 286T1224 | | | FORWARD ENTRY DOOR CONTROL,L FWD ATTEND. PNL (continued) | | | | | | | | | | | | |
| 008 | 22 | | PA | | 12-0 | 52-11-12 | SM00001 | | | | 9 | | | | ALL | |
| 009 | 22 | | PA | | 31-0 | 52-11-12 | D04290P | | | | 34 | | | | 050-099 | |
| 009 | 22 | | PA | | 30-0 | 52-11-12 | D04290P | | | | 34 | | | | 150-199, 275-299 | |
| 010 | 22 | | PA | | 6-0 | 52-11-12 | SM00001 | | | | 9 | | | | 050-099, 275-299 | |
| 010 | 22 | | PA | | 4-0 | 52-11-12 | SM00001 | | | | 9 | | | | 150-199 | |
| 011 | 20 | | PA | | 6-10 | 52-11-12 | SP00762 | | | | 9 | | D.. | 2 | 050-099, 275-278 | |
| 011 | 20 | | PA | | 7-0 | 52-11-12 | SP00762 | | | | 9 | | D.. | 2 | 150-199 | |
| 011 | 20 | | PA | | 5-4 | 52-11-12 | SP00762 | | | | 9 | | D.. | 2 | 280-299 | |
| 012 | 22 | | PA | | 13-0 | 52-11-12 | D01646 | | | | 25 | | | 4 | C | 050-099, 275-299 |
| 012 | 22 | | PA | | 12-0 | 52-11-12 | D01646 | | | | 25 | | | 4 | C | 150-199 |
| 013 | 22 | | PA | | 13-0 | 52-11-12 | D01646 | | | | 27 | | | 3 | C | 050-099, 275-299 |
| 013 | 22 | | PA | | 12-0 | 52-11-12 | D01646 | | | | 27 | | | 3 | C | 150-199 |
| 014 | 22 | | PA | | 31-0 | 52-11-12 | D01646 | | | | 28 | | | 12 | | 050-099 |
| 014 | 22 | | PA | | 30-0 | 52-11-12 | D01646 | | | | 28 | | | 12 | | 150-199, 275-299 |
| 015 | 20 | | PA | | 11-0 | 33-24-14 | L00670 | | | | FSB | | | 51 | | 275-278 |
| 015 | 20 | | PA | | 9-8 | 33-24-14 | L00670 | | | | FSB | | | 51 | | 280-299 |
| 016 | 20 | | PA | | 11-0 | 33-24-14 | L00670 | | | | NS | | | 52 | | 275-278 |
| 016 | 20 | | PA | | 9-8 | 33-24-14 | L00670 | | | | NS | | | 52 | | 280-299 |
| 017 | 20 | | PA | | 6-0 | 33-24-14 | L00670 | | | | GND | | | A.. | 2 | 275-278 |
| 017 | 20 | | PA | | 6-9 | 33-24-14 | L00670 | | | | GND | | | A.. | 2 | 280-299 |
| 018 | 20 | | PA | | 11-0 | 52-11-12 | D01646 | | | | 22 | | | D.. | 2 | 050-099, 275-299 |
| 018 | 20 | | PA | | 9-0 | 52-11-12 | D01646 | | | | 22 | | | D.. | 2 | 150-199 |
| 019 | 20 | | PA | | 18-0 | 33-22-31 | D01646 | | | | 15 | | | =P | C | 050-099 |
| 019 | 20 | | PA | | 16-0 | 33-22-31 | D01646 | | | | 15 | | | =P | C | 150-199 |
| 019 | 20 | | PA | | 16-3 | 33-22-31 | D01646 | | | | 15 | | | =P | C | 275-299 |
| 020 | 20 | | PA | | 30-0 | 33-22-31 | D01646 | | | | 16 | | | 3 | | 275-299 |
| 021 | 20 | | PA | | 4-4 | 33-22-31 | L00184 | | | | =G | | | A.. | 2 | 050-099 |
| 021 | 20 | | PA | | 4-0 | 33-22-31 | L00184 | | | | =G | | | A.. | 2 | 150-199 |
| 021 | 20 | | PA | | 3-0 | 33-22-31 | L00184 | | | | =G | | | A.. | 2 | 275-299 |
| 022 | 22 | | PA | | 31-0 | 33-21-21 | D01646 | | | | 31 | | | 4 | | 050-099 |
| 022 | 22 | | PA | | 30-0 | 33-21-21 | D01646 | | | | 31 | | | | S | 150-199 |
| 022 | 24 | | PK | | 30-0 | 33-21-21 | D01646 | | | | 31 | | | 4 | | 275-299 |
| 023 | 22 | | PA | | 31-0 | 33-21-21 | D01646 | | | | 32 | | | 5 | | 050-099 |
| 023 | 22 | | PA | | 30-0 | 33-21-21 | D01646 | | | | 32 | | | 5 | | 150-199 |
| 023 | 24 | | PK | | 30-0 | 33-21-21 | D01646 | | | | 32 | | | 5 | | 275-299 |
| 027 | 22 | | PA | | 1-0 | 52-11-12 | S00410 | | | | 2 | | | 6 | C | ALL |
| 028 | 22 | | PA | | 13-0 | 52-11-12 | D01646 | | | | 49 | | | 1 | C | 050-099, 275-299 |
| 028 | 22 | | PA | | 12-0 | 52-11-12 | D01646 | | | | 49 | | | 1 | C | 150-199 |
| 029 | 22 | | PA | | 13-0 | 52-11-12 | D01646 | | | | 48 | | | 5 | C | 050-099, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|---|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1224 | 286T1224 | | | FORWARD ENTRY DOOR CONTROL,L FWD ATTEND. PNL (continued) | | | | | | | | | | | | | |
| 029 | 22 | | PA | 12-0 | 52-11-12 | D01646 | | 48 | | | | | S00410 | 5 | C | | 150-199 |
| 030 | 22 | | PA | 23-0 | 52-11-12 | D04290P | | 1 | | | | | S00410 | 6 | C | | 050-099 |
| 030 | 22 | | PA | 24-0 | 52-11-12 | D04290P | | 1 | | | | | S00410 | 6 | C | | 150-199, 275-299 |
| 031 | 20 | | PA | 31-0 | 33-22-11 | D01646 | | 13 | | | | | D04290P | 13 | | | 050-099 |
| 031 | 20 | | PA | 30-0 | 33-22-11 | D01646 | | 13 | | | | | D04290P | 13 | | | 150-199, 275-299 |
| 032 | 20 | | PA | 31-0 | 33-22-11 | D01646 | | 14 | | | | | D04290P | 14 | | | 050-099 |
| 032 | 20 | | PA | 30-0 | 33-22-11 | D01646 | | 14 | | | | | D04290P | 14 | | | 150-199, 275-299 |
| 033 | 20 | | PA | 37-0 | 33-22-11 | D01646 | | 12 | | | | | L00182 | =P | C | | 050-099 |
| 033 | 20 | | PA | 36-0 | 33-22-11 | D01646 | | 12 | | | | | L00182 | =P | C | | 150-199, 275-299 |
| 034 | 20 | | PA | 31-0 | 33-22-11 | D01646 | | 21 | | | | | D04290P | 17 | | | 050-099 |
| 034 | 20 | | PA | 30-0 | 33-22-11 | D01646 | | 21 | | | | | D04290P | 17 | | | 150-199, 275-299 |
| 035 | 20 | | PA | 8-0 | 33-22-11 | L00182 | | =G | | C | | | GD03932 | A.. | 2 | | ALL |
| 036 | 24 | | PK | 31-0 | 33-22-11 | D01646 | | 35 | | | | | D04290P | 18 | | | 050-099 |
| 036 | 24 | | PK | 30-0 | 33-22-11 | D01646 | | 35 | | | | | D04290P | 18 | | | 150-199, 275-299 |
| 037 | 24 | | PK | 31-0 | 33-22-11 | D01646 | | 36 | | | | | D04290P | 15 | | | 050-099 |
| 037 | 24 | | PK | 30-0 | 33-22-11 | D01646 | | 36 | | | | | D04290P | 15 | | | 150-199, 275-299 |
| 038 | 24 | | PK | 31-0 | 33-22-11 | D01646 | | 34 | | | | | D04290P | 16 | | | 050-099 |
| 038 | 24 | | PK | 30-0 | 33-22-11 | D01646 | | 34 | | | | | D04290P | 16 | | | 150-199, 275-299 |
| 040 | 24 | | PK | 31-0 | 33-21-31 | D01646 | | 2 | | | | | D04290P | 19 | | | 050-099 |
| 040 | 24 | | PK | 30-0 | 33-21-31 | D01646 | | 2 | | | | | D04290P | 19 | | | 150-199, 275-299 |
| 041 | 20 | | PA | 11-0 | 33-21-31 | D01646 | | 6 | | | | | GD00017 | A.. | 2 | | 050-099, 275-299 |
| 041 | 20 | | PA | 9-0 | 33-21-31 | D01646 | | 6 | | | | | GD00017 | A.. | 2 | | 150-199 |
| 042 | 22 | | PA | 6-0 | 33-24-12 | D04290P | | 20 | | | | | D13442J | 18 | | | 050-099 |
| 042 | 22 | | PA | 5-0 | 33-24-12 | D04290P | | 20 | | | | | D13442J | 18 | | | 150-199 |
| 042 | 20 | | PA | 10-0 | 33-24-12 | D04290P | | 20 | | | | | L00414 | NS | C | | 275-299 |
| 043 | 22 | | PA | 6-0 | 33-24-12 | D04290P | | 21 | | | | | D13442J | 16 | | | 050-099 |
| 043 | 22 | | PA | 5-0 | 33-24-12 | D04290P | | 21 | | | | | D13442J | 16 | | | 150-199 |
| 043 | 20 | | PA | 10-0 | 33-24-12 | D04290P | | 21 | | | | | L00414 | FSB | C | | 275-299 |
| 049 | 20 | | PA | 8-0 | 33-24-12 | GD03932 | | A.. | | 2 | | | L00414 | GND | C | | 275-299 |
| 055 | 22 | | PA | 31-0 | 33-51-11 | D01646 | | 37 | | | | | D04290P | 27 | | | 050-099 |
| 055 | 22 | | PA | 30-0 | 33-51-11 | D01646 | | 37 | | | | | D04290P | 27 | | | 150-199, 275-299 |
| 056 | 20 | | PA | 11-0 | 33-51-11 | D01646 | | 38 | | | | | GD00017 | D.. | 2 | | 050-099, 275-299 |
| 056 | 20 | | PA | 9-0 | 33-21-11 | D01646 | | 38 | | | | | GD00017 | D.. | 2 | | 150-199 |
| 057 | 18 | | PA | 11-0 | 33-51-11 | D01646 | | 11 | | DK | | | GD00017 | A.. | 2 | | 050-099, 275-299 |
| 057 | 18 | | PA | 9-0 | 33-51-11 | D01646 | | 11 | | DK | | | GD00017 | A.. | 2 | | 150-199 |
| 058 | 24 | | PK | 31-0 | 33-21-11 | D01646 | | 9 | | | | | D04290P | 28 | | | 050-099 |
| 058 | 24 | | PK | 30-0 | 33-21-11 | D01646 | | 9 | | | | | D04290P | 28 | | | 150-199, 275-299 |
| 059 | 20 | | PA | 11-0 | 33-21-11 | D01646 | | 10 | | | | | GD00017 | A.. | 2 | | 050-099, 275-299 |
| 059 | 20 | | PA | 9-0 | 33-21-11 | D01646 | | 10 | | | | | GD00017 | A.. | 2 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1224 | 286T1224 | | | FORWARD ENTRY DOOR CONTROL,L FWD ATTEND. PNL (continued) | | | | | | | | | | | | | |
| 060 | 24 | | PK | 31-0 | 33-21-11 | D01646 | | 7 | | | | | D04290P | 29 | | | 050-099 |
| 060 | 24 | | PK | 30-0 | 33-21-11 | D01646 | | 7 | | | | | D04290P | 29 | | | 150-199, 275-299 |
| 061 | 22 | | PA | 36-0 | 31-31-26 | D05126P | | 7 | | | | | D04290P | 35 | | | 050-099 |
| 061 | 24 | | PK | 37-0 | 31-31-26 | D05126P | | 7 | | | | | D04290P | 35 | | | 150-199 |
| 061 | 24 | | PK | 36-0 | 31-31-26 | D05126P | | 7 | | | | | D04290P | 35 | | | 275-299 |
| 062 | 22 | | PA | 36-0 | 52-11-12 | D05126P | | 8 | | | | | D04290P | 36 | | | 050-099 |
| 062 | 22 | | PA | 37-0 | 52-11-12 | D05126P | | 8 | | | | | D04290P | 36 | | | 150-199 |
| 062 | 20 | | PA | 36-0 | 52-11-12 | D05126P | | 8 | | | | | D04290P | 36 | | | 275-299 |
| 064 | 24 | | PK | 36-0 | 23-31-13 | D05126P | | 9 | | | | | D04290P | 41 | | | 050-099, 275-299 |
| 064 | 24 | | PK | 37-0 | 23-31-13 | D05126P | | 9 | | | | | D04290P | 41 | | | 150-199 |
| 068 | 20 | | PA | 28-0 | 33-26-21 | D04290P | | 44 | | | | | L00755 | 2 | B | | 050-099 |
| 068 | 20 | | PA | 28-0 | 33-26-21 | L00755 | | 2 | B | | | | D04290P | 44 | | | 150-199 |
| 068 | 22 | | PA | 28-0 | 33-26-21 | L00755 | | 2 | B | | | | D04290P | 44 | | | 275-299 |
| 069 | 22 | | PA | 30-0 | 33-22-42 | D04290P | | 55 | | | | | D01646 | 5 | | | 275-299 |
| 070 | 22 | | PA | 22-0 | 33-22-41 | D01646 | | 1 | | | | | SM00020 | 9 | | | 050-099 |
| 070 | 22 | | PA | 19-0 | 33-22-41 | D01646 | | 1 | | | | | SM00020 | 9 | | | 150-199 |
| 070 | 22 | | PA | 30-0 | 33-22-41 | D01646 | | 1 | | | | | D04290P | 6 | | | 275-299 |
| 071 | 22 | | PA | 22-0 | 33-22-41 | D01646 | | 3 | | | | | SM00004 | 9 | | | 275-299 |
| 072 | 22 | | PA | 30-0 | 33-22-41 | D01646 | | 4 | | | | | D04290P | 26 | | | 050-099, 150-199 |
| 072 | 22 | | PA | 23-0 | 33-22-41 | D01646 | | 4 | | | | | D06062J | 5 | | | 275-299 |
| 073 | 22 | | PA | 31-0 | 33-22-41 | D01646 | | 8 | | | | | D04290P | 53 | | | 050-099 |
| 073 | 22 | | PA | 30-0 | 33-22-41 | D01646 | | 8 | | | | | D04290P | 53 | | | 150-199 |
| 073 | 22 | | PA | 22-0 | 33-22-41 | D01646 | | 8 | | | | | SM00002 | 9 | | | 275-299 |
| 074 | 22 | | PA | 30-0 | 33-22-41 | D04290P | | 9 | | | | | D01646 | 3 | | | 050-099, 150-199 |
| 074 | 22 | | PA | 31-0 | 33-22-41 | D04290P | | 9 | | | | | SM00004 | 9 | | | 275-299 |
| 077 | 20 | | PA | 12-0 | 33-22-41 | D06062J | | 8 | | | | | GD03932 | A.. 2 | | | 050-099, 150-199 |
| 077 | 20 | | PA | 14-0 | 33-22-41 | D06062J | | 8 | | | | | GD03932 | A.. 2 | | | 275-299 |
| 078 | 22 | | PA | 7-0 | 33-22-41 | D06062J | | 1 | | | | | SM00002 | 9 | | | 050-099 |
| 078 | 22 | | PA | 6-0 | 33-22-41 | SM00002 | | 9 | | | | | D06062J | 1 | | | 150-199 |
| 078 | 22 | | PA | 5-0 | 33-22-41 | D06062J | | 1 | | | | | SM00002 | 9 | | | 275-299 |
| 079 | 22 | | PA | 5-0 | 33-22-41 | D04290P | | 40 | | | | | SM00002 | 9 | | | 050-099 |
| 079 | 22 | | PA | 5-0 | 33-22-41 | SM00002 | | 9 | | | | | D04290P | 40 | | | 150-199 |
| 079 | 22 | | PA | 11-0 | 33-22-41 | D04290P | | 40 | | | | | SM00002 | 9 | | | 275-299 |
| 086 | 20 | | PA | 12-0 | 33-22-41 | D06062J | | 7 | | | | | GD03932 | S.. 2 | | | 050-099, 150-199 |
| 086 | 20 | | PA | 14-0 | 33-22-41 | D06062J | | 7 | | | | | GD03932 | S.. 2 | | | 275-299 |
| 087 | 22 | | PA | 10-0 | 33-22-41 | D06062J | | 10 | | | | | D04290P | 49 | | | 050-099 |
| 087 | 22 | | PA | 5-0 | 33-22-41 | D06062J | | 10 | | | | | SM00004 | 9 | | | 275-299 |
| 088 | 20 | | PA | 12-0 | 33-22-41 | D06062J | | 9 | | | | | GD03932 | A.. 2 | | | ALL |
| 095 | 20 | | PA | 12-0 | 33-22-41 | D06062J | | 11 | | | | | GD03932 | A.. 2 | | | 050-099, 150-199 |

WIRE LIST
D280T132

91-21-11
Section W1220
Page 15
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|----|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1224 | 286T1224 | | | FORWARD ENTRY DOOR CONTROL,L FWD ATTEND. PNL (continued) | | | | | | | | | | | | | |
| 095 | 20 | | PA | 14-0 | 33-22-41 | D06062J | | 11 | | | | | GD03932 | A.. | 2 | | 275-299 |
| 102 | 20 | | PA | 32-0 | 33-22-31 | D01646 | | 53 | | | | | SP00244 | | S | | 050-099 |
| 102 | 20 | | PA | 31-0 | 33-22-31 | D01646 | | 53 | | | | | SP00244 | | S | | 150-199 |
| 104 | 20 | | PA | 19-0 | 33-21-31 | STA0437 | | | CAP | Y | | | D04290P | | 49 | | 150, 153-157 |
| 104 | 20 | | PA | 19-0 | 33-21-31 | S00789 | | | =P | C | | | D04290P | | 49 | | 151-152 |
| 105 | 22 | | PA | 20-0 | 33-22-41 | SM00020 | | | | 9 | | | SP02450 | | 9 | | 050-099 |
| 105 | 22 | | PA | 18-0 | 33-22-41 | SM00020 | | | | 9 | | | SP02450 | | 9 | | 150-199 |
| 105 | 22 | | PA | 34-0 | 33-22-41 | D04290P | | | | 8 | | | SP02450 | | 9 | | 275-299 |
| 106 | 22 | | PA | 28-0 | 33-22-41 | D04290P | | | | 10 | | | SP02452 | | 9 | | ALL |
| 107 | 22 | | PA | 14-4 | 33-22-41 | D04290P | | | | 7 | | | D06274J | =1 | | | 050-099, 275-299 |
| 107 | 22 | | PA | 16-0 | 33-22-41 | D06274J | | | | =1 | | | D04290P | | 7 | | 150-199 |
| 110 | 20 | | PA | 2-4 | 33-22-41 | D06272P | | | | =1 | | | GD00760 | A.. | 2 | | 050-099, 275-299 |
| 110 | 20 | | PA | 3-0 | 33-22-41 | D06272P | | | | =1 | | | GD00760 | A.. | 2 | | 150-199 |
| 111 | 24 | | PK | 31-0 | 24-51-51 | D01646 | | | | 17 | | | D04290P | | 22 | | 050-099 |
| 111 | 24 | | PK | 30-0 | 24-51-51 | D01646 | | | | 17 | | | D04290P | | 22 | | 150-199, 275-299 |
| 112 | 20 | | PA | 11-0 | 24-51-51 | D01646 | | | | 20 | | | GD00017 | D.. | 2 | | 050-099, 275-299 |
| 112 | 20 | | PA | 9-0 | 24-51-51 | D01646 | | | | 20 | | | GD00017 | D.. | 2 | | 150-199 |
| 113 | 24 | | PK | 31-0 | 24-51-51 | D01646 | | | | 19 | | | D04290P | | 24 | | 050-099 |
| 113 | 24 | | PK | 30-0 | 24-51-51 | D01646 | | | | 19 | | | D04290P | | 24 | | 150-199, 275-299 |
| 114 | 24 | | PK | 31-0 | 24-51-51 | D01646 | | | | 18 | | | D04290P | | 25 | | 050-099 |
| 114 | 24 | | PK | 30-0 | 24-51-51 | D01646 | | | | 18 | | | D04290P | | 25 | | 150-199, 275-299 |
| 117 | 22 | | PA | 31-0 | 33-51-11 | D04290P | | | | 37 | | | D01646 | | 43 | | 050-099 |
| 117 | 22 | | PA | 30-0 | 33-51-11 | D04290P | | | | 37 | | | D01646 | | 43 | | 150-199, 275-299 |
| 118 | 22 | | PA | 31-0 | 33-51-11 | D04290P | | | | 38 | | | D01646 | | 45 | | 050-099 |
| 118 | 22 | | PA | 30-0 | 33-51-11 | D04290P | | | | 38 | | | D01646 | | 45 | | 150-199, 275-299 |
| 119 | 22 | | PA | 31-0 | 33-51-11 | D04290P | | | | 39 | | | D01646 | | 33 | | 050-099 |
| 119 | 22 | | PA | 30-0 | 33-51-11 | D04290P | | | | 39 | | | D01646 | | 33 | | 150-199, 275-299 |
| 120 | 20 | | PA | 11-0 | 33-51-11 | GD00017 | | | D.. | 2 | | | D01646 | | 44 | | 050-099, 275-299 |
| 120 | 20 | | PA | 9-0 | 33-51-11 | GD00017 | | | D.. | 2 | | | D01646 | | 44 | | 150-199 |
| 123 | 20 | | PA | 11-0 | 33-24-13 | D04290P | | | | 23 | | | L00648 | FSB | C | | 275 |
| 123 | 20 | | PA | 11-0 | 33-24-13 | D04290P | | | | 23 | | | STA0341 | | * | | 276, 280-299 |
| 123 | 20 | | PA | 11-0 | 33-24-13 | D04290P | | | | 23 | | | L00648 | | 3 | C | 277-278 |
| 124 | 20 | | PA | 11-0 | 33-24-13 | D04290P | | | | 26 | | | L00648 | NS | C | | 275 |
| 124 | 20 | | PA | 11-0 | 33-24-13 | D04290P | | | | 26 | | | STA0341 | | * | | 276, 280-299 |
| 124 | 20 | | PA | 11-0 | 33-24-13 | D04290P | | | | 26 | | | L00648 | | 1 | C | 277-278 |
| 125 | 20 | | PA | 9-0 | 33-24-13 | L00648 | | | GND | C | | | GD00119 | A.. | 2 | | 275 |
| 125 | 20 | | PA | 9-0 | 33-24-13 | STA0341 | | | | * | | | GD00119 | A.. | 2 | | 276, 280-299 |
| 125 | 20 | | PA | 9-0 | 33-24-13 | L00648 | | | | 2 | | | GD00119 | A.. | 2 | | 277-278 |
| 126 | 24 | | PK | 30-0 | 33-21-12 | D01646 | | | | 52 | | | D04290P | | 55 | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1224 | 286T1224 | | | FORWARD ENTRY DOOR CONTROL,L FWD ATTEND. PNL (continued) | | | | | | | | | | | |
| 126 | 24 | | PK | | 30-0 | 33-21-21 | D04290P | | | 50 | D01646 | | 52 | | 280-299 |
| 127 | 24 | | PK | | 30-0 | 33-21-11 | D04290P | | | 45 | D01646 | | 53 | | 280-299 |
| 129 | 24 | | PK | | 30-0 | 33-21-11 | D01646 | | | 55 | D04290P | | 51 | | 050-099 |
| 129 | 20 | | PA | | 30-0 | 33-21-11 | D01646 | | | 55 | D04290P | | 51 | | 150-199 |
| 129 | 22 | | PA | | 31-0 | 33-22-42 | D01646 | | | 55 | D04290P | | 53 | | 280-299 |
| 130 | 24 | | PK | | 32-0 | 33-21-12 | D01646 | | | 57 | D13442J | | 7 | | 050-099 |
| 130 | 20 | | PA | | 30-0 | 33-21-12 | D01646 | | | 57 | D13442J | | 7 | | 150-199 |
| 133 | 24 | | PK | | 30-0 | 33-21-11 | D01646 | | | 58 | D04290P | | 43 | | 050-099, 150-199 |
| 133 | 24 | | PK | | 30-0 | 33-21-31 | D04290P | | | 42 | D01646 | | 50 | | 280-299 |
| 134 | 22 | | PA | | 30-0 | 33-21-21 | D01646 | | | 51 | D04290P | | 46 | | 050-099, 150-199 |
| 134 | 24 | | PK | | 30-0 | 33-21-11 | D04290P | | | 46 | D01646 | | 51 | | 280-299 |
| 141 | 24 | | PK | | 30-0 | 33-21-31 | D01646 | | | 46 | D04290P | | 47 | | 050-099, 150-199 |
| 142 | 24 | | PK | | 30-0 | 33-21-12 | D01646 | | | 47 | D04290P | | 6 | | 050-099, 150-199 |
| 143 | 24 | | PK | | 30-0 | 33-21-12 | D01646 | | | 56 | D04290P | | 23 | | 050-099, 150-199 |
| 145 | 22 | | PA | | 6-0 | 33-21-21 | D13442J | | | 1 | D04290P | | 54 | | 050-099 |
| 145 | 22 | | PK | | 5-0 | 33-21-21 | D13442J | | | 1 | D04290P | | 54 | | 150-199 |
| 146 | 22 | | PA | | 6-0 | 33-21-21 | D13442J | | | 2 | SM00005 | | | S | 050-099 |
| 146 | 22 | | PK | | 6-0 | 33-21-21 | D13442J | | | 2 | SM00008 | | | S | 150-199 |
| 147 | 22 | | PA | | 6-0 | 33-21-21 | D13442J | | | 3 | D04290P | | 56 | | 050-099 |
| 147 | 22 | | PA | | 5-0 | 33-21-21 | D13442J | | | 3 | D04290P | | 56 | | 150-199 |
| 148 | 20 | | PA | | 6-0 | 33-21-21 | D13442J | | | 4 | GD06735 | A.. | 2 | | 050-099 |
| 148 | 20 | | PA | | 5-0 | 33-21-21 | D13442J | | | 4 | GD06735 | A.. | 2 | | 150-199 |
| 149 | 22 | | PA | | 6-0 | 33-21-21 | D13442J | | | 5 | D04290P | | 57 | | 050-099 |
| 149 | 22 | | PA | | 5-0 | 33-21-21 | D13442J | | | 5 | D04290P | | 57 | | 150-199 |
| 150 | 20 | | PA | | 36-0 | 33-22-31 | D01646 | | | 54 | SP00246 | | | S | 050-099 |
| 150 | 20 | | PA | | 35-0 | 33-22-31 | D01646 | | | 54 | SP00246 | | | S | 150-199 |
| 151 | 20 | | PA | | 6-0 | 33-22-32 | D04290P | | | 50 | D13442J | | 13 | | 050-099 |
| 151 | 20 | | PA | | 6-0 | 33-22-32 | D13442J | | | 13 | D04290P | | 50 | | 150-199 |
| 152 | 20 | | PA | | 6-0 | 33-22-32 | D13442J | | | 14 | GD06735 | A.. | 2 | | 050-099 |
| 152 | 20 | | PA | | 5-0 | 33-22-32 | D13442J | | | 14 | GD06735 | A.. | 2 | | 150-199 |
| 153 | 20 | | PA | | 6-0 | 33-22-32 | D13442J | | | 15 | GD06735 | S.. | 2 | | 050-099 |
| 153 | 20 | | PA | | 5-0 | 33-22-32 | D13442J | | | 15 | GD06735 | S.. | 2 | | 150-199 |
| 154 | 20 | | PA | | 17-0 | 33-22-32 | D04290P | | | 52 | D10940 | | 1 | | 050-099 |
| 154 | 20 | | PA | | 14-0 | 33-22-32 | D10940 | | | 1 | D04290P | | 52 | | 150-199 |
| 155 | 20 | | PA | | 7-0 | 33-22-32 | D10940 | | | 2 | GD01022 | A.. | E | | 050-099 |
| 155 | 20 | | PA | | 13-0 | 33-22-32 | D10940 | | | 2 | GD01022 | A.. | E | | 150-199 |
| 156 | 22 | | PA | | 10-0 | 33-22-41 | D04290P | | | 8 | SM00020 | | 9 | | 050-099 |
| 156 | 22 | | PA | | 13-0 | 33-22-41 | SM00020 | | | | D04290P | | 8 | | 150-199 |
| 162 | 20 | | PA | | 6-0 | 33-24-12 | D13442J | | | 17 | GD06735 | D.. | 2 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W1220
Page 17
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|----|-----------------|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1224 | | 286T1224 | | | FORWARD ENTRY DOOR CONTROL,L FWD ATTEND. PNL (continued) | | | | | | | | | | | |
| 162 | 20 | | PA | | 5-0 | 33-24-12 | GD06735 | A.. | 2 | | D13442J | 17 | | | 150-199 | |
| 167 | 24 | | PK | | 6-0 | 33-21-31 | D13442J | 6 | | | D04290P | 58 | | | 050-099 | |
| 167 | 24 | | PK | | 5-0 | 33-21-31 | D13442J | 6 | | | D04290P | 58 | | | 150-199 | |
| 169 | 24 | | PK | | 6-0 | 33-21-31 | D13442J | 8 | | | D04290P | 59 | | | 050-099 | |
| 169 | 24 | | PK | | 5-0 | 33-21-31 | D13442J | 8 | | | D04290P | 59 | | | 150-199 | |
| 170 | 24 | | PK | | 6-0 | 33-21-31 | D13442J | 12 | | | D04290P | 60 | | | 050-099 | |
| 170 | 20 | | PA | | 5-0 | 33-21-31 | D13442J | 12 | | | D04290P | 60 | | | 150-157 | |
| 170 | 24 | | PK | | 5-0 | 33-21-31 | D13442J | 12 | | | D04290P | 60 | | | 162-199 | |
| 171 | 24 | | PK | | 6-0 | 33-21-31 | D13442J | 9 | | | D04290P | 61 | | | 050-099 | |
| 171 | 24 | | PK | | 5-0 | 33-21-31 | D13442J | 9 | | | D04290P | 61 | | | 150-199 | |
| 173 | 20 | | PA | | 6-0 | 33-21-31 | D13442J | 11 | | | GD06735 | A.. | 2 | | 050-099 | |
| 173 | 20 | | PA | | 5-0 | 33-21-31 | D13442J | 11 | | | GD06735 | A.. | 2 | | 150-199 | |
| 174 | 20 | | PA | | 12-0 | 33-21-31 | STA0437 | CAP | Y | | GD00938 | A.. | 2 | | 150, 153-157 | |
| 174 | 20 | | PA | | 12-0 | 33-21-31 | S00789 | =G | C | | GD00938 | A.. | 2 | | 151-152 | |
| 608 | 22 | | PA | | 10-0 | 33-22-41 | D04290P | 45 | | | D06062J | 5 | | | 050-099 | |
| 608 | 20 | | PA | | 9-0 | 33-22-41 | D06062J | 5 | | | D04290P | 45 | | | 150-199 | |
| 800 | 20 | | PA | | 10-0 | 33-27-11 | D01646 | 60 | | | GD00017 | A.. | 2 | | 050-099, 150-199 | |
| 801 | 22 | | PA | | 30-0 | 33-27-11 | D01646 | 61 | | | D04290P | 3 | | | 050-099 | |
| 801 | 20 | | PA | | 30-0 | 33-27-11 | D01646 | 61 | | | D04290P | 3 | | | 150-199 | |
| 802 | 22 | | PA | | 30-0 | 33-27-11 | D01646 | 59 | | | D04290P | 11 | | | 050-099 | |
| 802 | 20 | | PA | | 30-0 | 33-27-11 | D01646 | 59 | | | D04290P | 11 | | | 150-199 | |
| 807 | 20 | | PA | | 6-0 | 33-22-41 | D06148J | 1 | | | GD04198 | A.. | 2 | | 050-099 | |
| 807 | 20 | | PA | | 3-0 | 33-22-41 | D06148J | 1 | | | GD04876 | A.. | 2 | | 150-199 | |
| 808 | 20 | | PA | | 56-0 | 33-22-41 | D06148J | 2 | | | SM00005 | S | | | 050-099 | |
| 808 | 20 | | PA | | 46-0 | 33-22-41 | D06148J | 2 | | | SM00005 | S | | | 150-199 | |
| 809 | 20 | | PA | | 14-0 | 33-22-41 | L01060 | =G | C | | GD04194 | A.. | 2 | | 050-099 | |
| 809 | 20 | | PA | | 13-0 | 33-22-41 | L01060 | =G | C | * | GD04194 | A.. | 2 | | 150-157 | |
| 810 | 20 | | PA | | 13-0 | 33-22-41 | L01060 | =P | C | | SM00005 | S | | | 050-099 | |
| 810 | 20 | | PA | | 12-0 | 33-22-41 | L01060 | =P | C | * | SM00005 | S | | | 150-157 | |
| 811 | 22 | | PA | | 23-0 | 33-22-41 | L01060 | =P | C | * | L01059 | =P | C | | 150-157 | |
| 812 | 22 | | PA | | 23-0 | 33-22-41 | L01060 | =G | C | * | L01059 | =G | C | | 150-157 | |
| 814 | 22 | | PA | | 5-0 | 33-22-41 | D04290P | 42 | | | SM00002 | 9 | | | 050-099 | |
| 814 | 22 | | PA | | 5-0 | 33-22-41 | SM00002 | | 9 | | D04290P | 42 | | | 150-199 | |
| 815 | 20 | | PA | | 5-0 | 33-22-41 | D04290P | 48 | | | SM00005 | S | | | 050-099, 150-199 | |
| 816 | 22 | | PA | | 11-0 | 33-22-41 | SP03984 | | 9 | | D06062J | 10 | | | 150-199 | |
| 922 | 22 | | PA | | 30-0 | 33-21-21 | D04290P | | 4 | | SM00008 | S | | | 150-199 | |
| A-A | | | | | 0-0 | 52-11-12 | SP00760 | | 9 | | M00778 | =P | | | ALL | |
| A-B | | | | | 0-0 | 52-11-12 | SP00762 | | 9 | | M00778 | =G | | | ALL | |
| B-A | | | | | 0-0 | 33-22-41 | S00460 | RED | | | SP02450 | 9 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 18

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1224 | 286T1224 | | | FORWARD ENTRY DOOR CONTROL,L FWD ATTEND. PNL (continued) | | | | | | | | | | | |
| B-B | | | | | 0-0 | 33-22-41 | S00460 | | BLU | | SP02452 | | 9 | | ALL |
| W1226 | 286T1226 | | | E1 TO P19 DC FEEDER & DOOR SENSORS | | | | | | | | | | | |
| 001 | 24 | | PK | | 31-0 | 33-22-11 | D05130J | | | 5 | D05090P | | 1 | | ALL |
| 002 | 24 | | PK | | 31-0 | 33-22-11 | D05130J | | | 6 | D05090P | | 2 | | ALL |
| 003 | 24 | | PK | | 31-0 | 33-22-11 | D05130J | | | 3 | D05090P | | 3 | | ALL |
| 004 | 24 | | PK | | 31-0 | 33-22-11 | D05130J | | | 4 | D05090P | | 4 | | ALL |
| 005 | 22 | | PA | | 39-0 | 33-25-11 | D05678J | | | 3 | D05090P | | 5 | | 050-099 |
| 006 | 20 | | PA | | 31-0 | 33-51-21 | D05090P | | | 12 | D05130J | | 1 | | ALL |
| 007 | 20 | | PA | | 31-0 | 33-51-21 | D05090P | | | 13 | D05130J | | 2 | | ALL |
| 008 | 22 | | PA | | 31-0 | 52-11-12 | D05090P | | | 14 | D05130J | | 40 | | ALL |
| 009 | 22 | | PA | | 31-0 | 52-11-12 | D05090P | | | 15 | D05130J | | 41 | | ALL |
| 010 | 22 | | PA | | 31-0 | 52-11-12 | D05090P | | | 16 | D05130J | | 42 | | ALL |
| 011 | 24 | | PK | | 31-0 | 52-11-12 | D05090P | | | 17 | D05130J | | 43 | | ALL |
| 012 | 22 | | PA | | 39-0 | 23-31-11 | D05090P | | | 18 | D05678J | | 4 | | ALL |
| 013 | 22 | | PA | | 39-0 | 23-31-11 | D05090P | | | 19 | D05678J | | 5 | | ALL |
| 048 | 22 | | PA | | 31-0 | 21-66-11 | D05090P | | | 55 | D05130J | | 48 | | 050-099, 162-199 |
| 049 | 22 | | PA | | 31-0 | 21-66-11 | D05090P | | | 42 | D05130J | | 7 | | 050-099, 162-199 |
| 050 | 22 | | PA | | 31-0 | 21-66-11 | D05090P | | | 43 | D05130J | | 8 | | 050-099, 162-199 |
| 051 | 22 | | PA | | 31-0 | 21-66-11 | D05090P | | | 44 | D05130J | | 9 | | 050-099, 162-199 |
| 201B | 24 | | PL | A | 47-0 | 52-11-13 | D05130J | | | 11 | SP00252 | | 9 | | ALL |
| 201R | 24 | | PL | A | 0-0 | 52-11-13 | D05130J | | | 10 | SP00250 | | 9 | | ALL |
| 202B | 24 | | PL | B | 50-0 | 52-11-13 | D05130J | | | 13 | SP00256 | | 9 | | ALL |
| 202R | 24 | | PL | B | 0-0 | 52-11-13 | D05130J | | | 12 | SP00254 | | 9 | | ALL |
| 203B | 24 | | PL | C | 44-0 | 52-11-13 | D05130J | | | 15 | SP00260 | | 9 | | ALL |
| 203R | 24 | | PL | C | 0-0 | 52-11-13 | D05130J | | | 14 | SP00258 | | 9 | | ALL |
| 204B | 24 | | PL | D | 47-0 | 52-11-13 | D05130J | | | 17 | SP00264 | | 9 | | ALL |
| 204R | 24 | | PL | D | 0-0 | 52-11-13 | D05130J | | | 16 | SP00262 | | 9 | | ALL |
| 205B | 22 | | PB | E | 39-0 | 23-31-14 | D05678J | | | 9 | D05090P | | 7 | | 050-099, 150-199 |
| 205B | 22 | | PB | E | 39-0 | 23-31-14 | D05678J | | | 2 | D05090P | | 7 | | 275-299 |
| 205R | 22 | | PB | E | 0-0 | 23-31-14 | D05678J | | | 8 | D05090P | | 6 | | 050-099, 150-199 |
| 205R | 22 | | PB | E | 0-0 | 23-31-14 | D05678J | | | 1 | D05090P | | 6 | | 275-299 |
| 206B | 22 | | PB | F | 44-0 | 21-51-22 | D05090P | | | 8 | D05738J | | 1 | | ALL |
| 206R | 22 | | PB | F | 0-0 | 21-51-22 | D05090P | | | 9 | D05738J | | 2 | | ALL |
| 207B | 24 | | PL | G | 44-0 | 21-61-31 | D05090P | | | 10 | D05738J | | 3 | | ALL |
| 207R | 24 | | PL | G | 0-0 | 21-61-31 | D05090P | | | 11 | D05738J | | 4 | | ALL |
| 208B | 24 | | PL | CA | 44-0 | 52-71-11 | D05130J | | | 19 | SP00666 | | 9 | | ALL |
| 208R | 24 | | PL | CA | 0-0 | 52-71-11 | D05130J | | | 18 | SP00664 | | 9 | | ALL |
| 209B | 24 | | PL | CB | 44-0 | 52-71-11 | D05130J | | | 21 | SP00670 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 19

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1226 | 286T1226 | | | E1 TO P19 DC FEEDER & DOOR SENSORS (continued) | | | | | | | | | | | | | |
| 209R | 24 | PL | CB | 0-0 | 52-71-11 | D05130J | | 20 | | | | | SP00668 | | 9 | | ALL |
| 210B | 24 | PL | CC | 31-0 | 52-71-11 | D05130J | | 23 | | | | | D05090P | 23 | | | ALL |
| 210R | 24 | PL | CC | 0-0 | 52-71-11 | D05130J | | 22 | | | | | D05090P | 22 | | | ALL |
| 211B | 24 | PL | CD | 31-0 | 52-71-11 | D05130J | | 25 | | | | | D05090P | 25 | | | ALL |
| 211R | 24 | PL | CD | 0-0 | 52-71-11 | D05130J | | 24 | | | | | D05090P | 24 | | | ALL |
| 212B | 24 | PL | CE | 31-0 | 52-71-11 | D05130J | | 27 | | | | | D05090P | 27 | | | ALL |
| 212R | 24 | PL | CE | 0-0 | 52-71-11 | D05130J | | 26 | | | | | D05090P | 26 | | | ALL |
| 213B | 24 | PL | CF | 31-0 | 52-71-11 | D05130J | | 29 | | | | | D05090P | 29 | | | ALL |
| 213R | 24 | PL | CF | 0-0 | 52-71-11 | D05130J | | 28 | | | | | D05090P | 28 | | | ALL |
| 214B | 24 | PL | CG | 31-0 | 52-71-12 | D05130J | | 31 | | | | | D05090P | 31 | | | ALL |
| 214R | 24 | PL | CG | 0-0 | 52-71-12 | D05130J | | 30 | | | | | D05090P | 30 | | | ALL |
| 215B | 24 | PL | CH | 31-0 | 52-71-12 | D05130J | | 33 | | | | | D05090P | 33 | | | ALL |
| 215R | 24 | PL | CH | 0-0 | 52-71-12 | D05130J | | 32 | | | | | D05090P | 32 | | | ALL |
| 216B | 24 | PL | CL | 50-0 | 52-71-11 | D05130J | | 35 | | | | | SP00710 | | 9 | | ALL |
| 216R | 24 | PL | CL | 0-0 | 52-71-11 | D05130J | | 34 | | | | | SP00708 | | 9 | | ALL |
| 217B | 24 | PL | CM | 31-0 | 52-71-11 | D05130J | | 37 | | | | | D05090P | 37 | | | ALL |
| 217R | 24 | PL | CM | 0-0 | 52-71-11 | D05130J | | 36 | | | | | D05090P | 36 | | | ALL |
| 218B | 24 | PL | CN | 31-0 | 52-71-11 | D05130J | | 39 | | | | | D05090P | 39 | | | ALL |
| 218R | 24 | PL | CN | 0-0 | 52-71-11 | D05130J | | 38 | | | | | D05090P | 38 | | | ALL |
| 224B | 24 | PL | CU | 31-0 | 52-71-12 | D05130J | | 45 | | | | | D05090P | 21 | | | 150-199, 275-299 |
| 224R | 24 | PL | CU | 0-0 | 52-71-12 | D05130J | | 44 | | | | | D05090P | 20 | | | 150-199, 275-299 |
| 225B | 24 | PL | CV | 31-0 | 52-71-12 | D05130J | | 47 | | | | | D05090P | 35 | | | 150-199, 275-299 |
| 225R | 24 | PL | CV | 0-0 | 52-71-12 | D05130J | | 46 | | | | | D05090P | 34 | | | 150-199, 275-299 |
| 226B | 24 | PL | CW | 43-0 | 21-61-31 | D05738J | | 6 | | | | | D05090P | 40 | | | ALL |
| 226R | 24 | PL | CW | 0-0 | 21-61-31 | D05738J | | 7 | | | | | D05090P | 41 | | | ALL |
| 227B | 24 | PL | CX | 43-0 | 21-61-41 | D05738J | | 9 | | | | | D05090P | 52 | | | ALL |
| 227R | 24 | PL | CX | 0-0 | 21-61-41 | D05738J | | 8 | | | | | D05090P | 51 | | | ALL |
| 228B | 24 | PL | CY | 43-0 | 21-61-41 | D05738J | | 11 | | | | | D05090P | 54 | | | ALL |
| 228R | 24 | PL | CY | 0-0 | 21-61-41 | D05738J | | 10 | | | | | D05090P | 53 | | | ALL |
| 229B | 22 | PB | JD | 39-0 | 23-31-14 | D05090P | | 46 | | | | | D05678J | 11 | | | 050-099 |
| 229B | 22 | PB | JD | 39-0 | 23-31-14 | D05678J | | 11 | | | | | D05090P | 46 | | | 150-199 |
| 229R | 22 | PB | JD | 0-0 | 23-31-14 | D05090P | | 45 | | | | | D05678J | 10 | | | 050-099 |
| 229R | 22 | PB | JD | 0-0 | 23-31-14 | D05678J | | 10 | | | | | D05090P | 45 | | | 150-199 |
| 230B | 22 | PB | JE | 39-0 | 23-31-14 | D05090P | | 48 | | | | | D05678J | 2 | | | 050-099 |
| 230B | 22 | PB | JE | 39-0 | 23-31-14 | D05678J | | 2 | | | | | D05090P | 48 | | | 150-199 |
| 230R | 22 | PB | JE | 0-0 | 23-31-14 | D05090P | | 47 | | | | | D05678J | 1 | | | 050-099 |
| 230R | 22 | PB | JE | 0-0 | 23-31-14 | D05678J | | 1 | | | | | D05090P | 47 | | | 150-199 |
| 231B | 22 | PB | JF | 39-0 | 23-31-14 | D05090P | | 50 | | | | | D05678J | 7 | | | 050-099 |
| 231B | 22 | PB | JF | 39-0 | 23-31-14 | D05678J | | 7 | | | | | D05090P | 50 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 20

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1226 | 286T1226 | | | E1 TO P19 DC FEEDER & DOOR SENSORS (continued) | | | | | | | | | | | |
| 231R | 22 | PB | JF | | 0-0 | 23-31-14 | D05090P | 49 | | | D05678J | 6 | | | 050-099 |
| 231R | 22 | PB | JF | | 0-0 | 23-31-14 | D05678J | 6 | | | D05090P | 49 | | | 150-199 |
| A-A | | | | | 0-0 | 52-11-13 | SP00250 | | 9 | | S00184 | RED | | | ALL |
| A-B | | | | | 0-0 | 52-11-13 | SP00252 | | 9 | | S00184 | BLU | | | ALL |
| B-A | | | | | 0-0 | 52-11-13 | SP00254 | | 9 | | S00185 | RED | | | ALL |
| B-B | | | | | 0-0 | 52-11-13 | SP00256 | | 9 | | S00185 | BLU | | | ALL |
| C-A | | | | | 0-0 | 52-11-13 | SP00258 | | 9 | | S00186 | RED | | | ALL |
| C-B | | | | | 0-0 | 52-11-13 | SP00260 | | 9 | | S00186 | BLU | | | ALL |
| D-A | | | | | 0-0 | 52-11-13 | SP00262 | | 9 | | S00187 | RED | | | ALL |
| D-B | | | | | 0-0 | 52-11-13 | SP00264 | | 9 | | S00187 | BLU | | | ALL |
| E-A | | | | | 0-0 | 52-71-11 | SP00664 | | 9 | | S00194 | RED | | | ALL |
| E-B | | | | | 0-0 | 52-71-11 | SP00666 | | 9 | | S00194 | BLU | | | ALL |
| F-A | | | | | 0-0 | 52-71-11 | SP00668 | | 9 | | S00195 | RED | | | ALL |
| F-B | | | | | 0-0 | 52-71-11 | SP00670 | | 9 | | S00195 | BLU | | | ALL |
| G-A | | | | | 0-0 | 52-71-11 | SP00708 | | 9 | | S00202 | RED | | | ALL |
| G-B | | | | | 0-0 | 52-71-11 | SP00710 | | 9 | | S00202 | BLU | | | ALL |
| W1228 | 286T1228 | | | P33,P37 TO P19 FEEDER | | | | | | | | | | | |
| 001 | 16 | PA | | | 35-0 | 38-13-11 | D05660P | 5 | | | D05134P | 11 | FM | | 050-099 |
| 001 | 16 | PA | | | 35-0 | 38-13-11 | D05660P | 5 | | | D05134P | 11 | | | 150-157, 275-299 |
| 001 | 16 | PA | | | 35-0 | 38-13-11 | D05660P | 5 | | | D05134P | 31 | | | 162-199 |
| 003 | 18 | PA | | | 12-0 | 21-26-11 | D05098P | 3 | | | D05660P | 1 | | | ALL |
| 004 | 18 | PA | | | 12-0 | 21-26-11 | D05098P | 4 | | | D05660P | 2 | | | ALL |
| 005 | 18 | PA | | | 12-0 | 21-26-11 | D05098P | 5 | | | D05660P | 3 | | | ALL |
| 006 | 22 | PA | | | 43-0 | 33-51-11 | D05098P | 2 | | | D05134P | 5 | | | ALL |
| 007 | 20 | PA | | | 35-0 | 27-61-18 | D05660P | 8 | | | D05134P | 12 | | | ALL |
| 008 | 20 | PA | | | 35-0 | 27-61-18 | D05660P | 7 | | | D05134P | 13 | | | ALL |
| 009 | 22 | PA | | | 35-0 | 33-21-21 | D05660P | 9 | | | D05134P | 19 | | | ALL |
| 023 | 18 | PA | | | 43-0 | 33-21-31 | D05098P | 13 | | | D05134P | 7 | DK | | 050-099 |
| 023 | 16 | PA | | | 43-0 | 33-21-31 | D05098P | 13 | | | D05134P | 7 | | | 150-157, 275-299 |
| 023 | 16 | PA | | | 43-0 | 33-21-31 | D05098P | 13 | | | D05134P | 29 | | | 162-199 |
| 024 | 18 | PA | | | 43-0 | 33-21-31 | D05098P | 14 | | | D05134P | 8 | DK | | 050-099 |
| 024 | 16 | PA | | | 43-0 | 33-21-31 | D05098P | 14 | | | D05134P | 8 | | | 150-157, 275-299 |
| 024 | 16 | PA | | | 43-0 | 33-21-31 | D05098P | 14 | | | D05134P | 30 | | | 162-199 |
| 027 | 16 | PA | | | 43-0 | 33-21-11 | D05134P | 1 | | | D05098P | 1 | | | ALL |
| 028 | 16 | PA | | | 43-0 | 33-21-12 | D05134P | 2 | FM | | D05098P | 8 | | | 050-099 |
| 028 | 16 | PA | | | 1-0 | 33-21-12 | SM00002 | | 9 | | D05098P | 8 | | | 150-199, 275-299 |
| 029 | 16 | PA | | | 43-0 | 33-21-12 | D05134P | 3 | FM | | D05098P | 9 | | | 050-099 |
| 029 | 16 | PA | | | 1-0 | 33-21-12 | SM00003 | | 9 | | D05098P | 9 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 21

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|---|------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1228 | 286T1228 | | | P33,P37 TO P19 FEEDER (continued) | | | | | | | | | | | | | | |
| 038 | 22 | | PA | | 11-11 | 33-22-11 | SP01456 | | | | 9 | | | D02932 | 9 | | | 050-099, 150-199 |
| 038 | 22 | | PA | | 7-10 | 33-22-11 | SP01456 | | | | 9 | | | D02932 | 9 | | | 275-299 |
| 039 | 22 | | PA | | 11-11 | 33-22-11 | SP01458 | | | | 9 | | | D02932 | 10 | | | 050-099, 150-199 |
| 039 | 22 | | PA | | 7-10 | 33-22-11 | SP01458 | | | | 9 | | | D02932 | 10 | | | 275-299 |
| 040 | 22 | | PA | | 11-11 | 33-22-11 | SP01460 | | | | 9 | | | D02932 | 12 | | | 050-099, 150-199 |
| 040 | 22 | | PA | | 7-10 | 33-22-11 | SP01460 | | | | 9 | | | D02932 | 12 | | | 275-299 |
| 041 | 22 | | PA | | 11-11 | 33-22-11 | SP01462 | | | | 9 | | | D02932 | 11 | | | 050-099, 150-199 |
| 041 | 22 | | PA | | 7-10 | 33-22-11 | SP01462 | | | | 9 | | | D02932 | 11 | | | 275-299 |
| 042 | 22 | | PA | | 10-0 | 33-22-11 | D02932 | | | | 5 | | | D05134P | 10 | | | 050-099 |
| 042 | 20 | | PA | | 10-0 | 33-22-11 | D02932 | | | | 5 | | | D05134P | 10 | | | 150-154, 162-165, 167-199 |
| 042 | 20 | | PQ | BQ | 11-0 | 33-22-11 | D02932 | | | | 5 | | | D05134P | 10 | | | 155-156 |
| 042 | 20 | | PA | | 11-0 | 33-22-11 | D02932 | | | | 5 | | | D05134P | 10 | | | 157, 275-299 |
| 042 | 20 | | PQ | BQ | 10-0 | 33-22-11 | D02932 | | | | 5 | | | D05134P | 10 | | | 166 |
| 042Z | | | | BQ | 0-0 | 33-22-11 | D02932 | | | | DED | | | D05134P | DED | | | 155-156, 166 |
| 043 | 20 | | PA | | 12-3 | 33-22-11 | D02932 | | | | 7 | | | GD03932 | A.. | 2 | | 050-099, 150-154, 157-165, 167-199 |
| 043 | 20 | | PQ | BR | 12-3 | 33-22-11 | D02932 | | | | 7 | | | GD03932 | A.. | 2 | | 155-156, 166 |
| 043 | 20 | | PA | | 7-1 | 33-22-11 | D02932 | | | | 7 | | | GD03932 | A.. | 2 | | 275-299 |
| 043Z | | | | BR | 0-0 | 33-22-11 | D02932 | | | | DED | | | GD03932 | DED | | | 155-156, 166 |
| 044 | 20 | | PA | | 12-3 | 33-22-11 | D02932 | | | | 8 | | | GD03932 | S.. | 2 | | 050-099, 150-199 |
| 044 | 20 | | PA | | 7-1 | 33-22-11 | D02932 | | | | 8 | | | GD03932 | S.. | 2 | | 275-299 |
| 045 | 20 | | PA | | 10-7 | 33-22-11 | L00191 | | | | =G | E | | GD03932 | S.. | 2 | | 050-099 |
| 045 | 20 | | PA | | 10-7 | 33-22-11 | L00191 | | | | =G | C | | GD03932 | S.. | 2 | | 150-199, 275-299 |
| 052 | 22 | | PA | | 15-9 | 33-22-41 | D01760 | | | | 5 | | | D05134P | 15 | | | ALL |
| 053 | 20 | | PA | | 3-4 | 33-22-41 | D01760 | | | | 7 | | | GD00760 | A.. | 2 | | ALL |
| 054 | 22 | | PA | | 6-7 | 33-22-41 | D01760 | | | | 8 | | | L00213 | =G | E | * | ALL |
| 055 | 22 | | PA | | 6-7 | 33-22-41 | D01760 | | | | 9 | | | SP01114 | | 9 | | ALL |
| 056 | 22 | | PA | | 6-7 | 33-22-41 | D01760 | | | | 10 | | | SP01116 | | 9 | | ALL |
| 057 | 22 | | PA | | 6-7 | 33-22-41 | D01760 | | | | 11 | | | SP01118 | | 9 | | ALL |
| 058 | 22 | | PA | | 6-7 | 33-22-41 | D01760 | | | | 12 | | | SP01120 | | 9 | | ALL |
| 059 | 20 | | PA | | 6-2 | 33-22-41 | L00213 | | | | =G | E | * | GD00760 | S.. | 2 | | ALL |
| 067 | 16 | | PA | | 35-0 | 38-13-11 | D05660P | | | | 11 | | | D05134P | 16 | FM | | 050-099 |
| 084 | 20 | | PA | | 35-0 | 33-44-11 | D05660P | | | | 6 | | | D05134P | 14 | | | ALL |
| 090 | 20 | | PA | | 15-2 | 33-27-11 | D02876 | | | | 5 | | | SM00007 | | 9 | | 050-099, 150-154, 157-165, 167-199 |
| 090 | 20 | | PQ | DO | 15-2 | 33-27-11 | D02876 | | | | 5 | | | SM00007 | | 9 | | 155-156, 166 |
| 090 | 20 | | PA | | 15-10 | 33-27-11 | D02876 | | | | 5 | | | D05134P | | 6 | | 275-299 |
| 090Z | | | | DO | 0-0 | 33-27-11 | D02876 | | | | DED | | | SM00007 | DED | | | 155-156, 166 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 22

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|---|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1228 | 286T1228 | | | P33,P37 TO P19 FEEDER (continued) | | | | | | | | | | | | | |
| 091 | 20 | | PA | 6-3 | 33-27-11 | D02876 | | 7 | | | | | GD01236 | A.. | 2 | | 050-099, 150-154, 157-165, 167-199, 275-299 |
| 091 | 20 | PQ | DP | 6-3 | 33-27-11 | D02876 | | 7 | | | | | GD01236 | A.. | 2 | | 155-156, 166 |
| 091Z | | | DP | 0-0 | 33-27-11 | D02876 | | DED | | | | | GD01236 | DED | | | 155-156, 166 |
| 092 | 20 | PA | | 5-4 | 33-27-11 | D02876 | | 8 | | | | | L00202 | =G | E | * | ALL |
| 093 | 22 | PA | | 4-10 | 33-27-11 | D02876 | | 9 | | | | | SP01226 | | 9 | | ALL |
| 094 | 22 | PA | | 4-10 | 33-27-11 | D02876 | | 10 | | | | | SP01228 | | 9 | | ALL |
| 095 | 22 | PA | | 4-10 | 33-27-11 | D02876 | | 11 | | | | | SP01230 | | 9 | | ALL |
| 096 | 22 | PA | | 4-10 | 33-27-11 | D02876 | | 12 | | | | | SP01232 | | 9 | | ALL |
| 097 | 20 | PA | | 3-4 | 33-27-11 | L00202 | | =G | E | * | | | GD01236 | S.. | 2 | | ALL |
| 098 | 20 | PA | | 15-0 | 33-27-11 | D02874 | | 5 | | | | | SM00006 | | 9 | | 050-099, 150-154, 157-165, 167-199 |
| 098 | 20 | PQ | DW | 15-0 | 33-27-11 | D02874 | | 5 | | | | | SM00006 | | 9 | | 155-156, 166 |
| 098 | 20 | PA | | 15-8 | 33-27-11 | D02874 | | 5 | | | | | D05134P | | 9 | | 275-299 |
| 098Z | | | DW | 0-0 | 33-27-11 | D02874 | | DED | | | | | SM00006 | DED | | | 155-156, 166 |
| 099 | 20 | PA | | 6-1 | 33-27-11 | D02874 | | 7 | | | | | GD01236 | A.. | 2 | | 050-099, 150-154, 157-165, 167-199, 275-299 |
| 099 | 20 | PQ | DX | 6-1 | 33-27-11 | D02874 | | 7 | | | | | GD01236 | A.. | 2 | | 155-156, 166 |
| 099Z | | | DX | 0-0 | 33-27-11 | D02874 | | DED | | | | | GD01236 | DED | | | 155-156, 166 |
| 100 | 20 | PA | | 5-2 | 33-27-11 | D02874 | | 8 | | | | | L00201 | =G | E | * | ALL |
| 101 | 22 | PA | | 4-8 | 33-27-11 | D02874 | | 9 | | | | | SP01234 | | 9 | | ALL |
| 102 | 22 | PA | | 4-8 | 33-27-11 | D02874 | | 10 | | | | | SP01236 | | 9 | | ALL |
| 103 | 22 | PA | | 4-8 | 33-27-11 | D02874 | | 11 | | | | | SP01238 | | 9 | | ALL |
| 104 | 22 | PA | | 4-8 | 33-27-11 | D02874 | | 12 | | | | | SP01240 | | 9 | | ALL |
| 105 | 20 | PA | | 3-4 | 33-27-11 | L00201 | | =G | E | * | | | GD01236 | S.. | 2 | | ALL |
| 106 | 18 | PA | | 17-0 | 33-27-11 | L01198 | | =P | C | | | | D05134P | | 32 | | 050-099 |
| 107 | 22 | PA | | 35-0 | 33-51-21 | D05660P | | 4 | | | | | D05134P | | 17 | | ALL |
| 108 | 22 | PA | | 35-0 | 33-51-21 | D05660P | | 10 | | | | | D05134P | | 18 | | ALL |
| 109 | 12 | PA | | 42-0 | 33-21-12 | SM00002 | | | 9 | | | | SM00004 | | 9 | | 150-199, 275-299 |
| 110 | 12 | PA | | 42-0 | 33-21-12 | SM00003 | | | 9 | | | | SM00005 | | 9 | | 150-199, 275-299 |
| 111 | 16 | PA | | 1-0 | 33-21-12 | SM00004 | | | 9 | | | | D05134P | | 2 | | 150-157, 275-299 |
| 111 | 16 | PA | | 1-0 | 33-21-12 | SM00004 | | | 9 | | | | D05134P | | 2 | FM | 162-199 |
| 112 | 16 | PA | | 1-0 | 33-21-12 | SM00005 | | | 9 | | | | D05134P | | 3 | | 150-157, 275-299 |
| 112 | 16 | PA | | 1-0 | 33-21-12 | SM00005 | | | 9 | | | | D05134P | | 3 | FM | 162-199 |
| 119 | 20 | PA | | 3-0 | 33-27-11 | SM00007 | | | 9 | | | | D05134P | | 6 | | 050-099 |
| 119 | 20 | PA | | 1-0 | 33-27-11 | D05134P | | | 6 | | | | SM00007 | | 9 | | 150-154, 157-165, 167-199 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 23

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1228 | 286T1228 | | | P33,P37 TO P19 FEEDER (continued) | | | | | | | | | | | | |
| 119 | 20 | PQ | ES | 1-0 | 33-27-11 | D05134P | | 6 | | | | SM00007 | | 9 | | 155-156, 166 |
| 119Z | | | ES | 0-0 | 33-27-11 | D05134P | | DED | | | | SM00007 | DED | | | 155-156, 166 |
| 120 | 20 | PA | | 3-0 | 33-27-11 | SM00006 | | | 9 | | | D05134P | 9 | | | 050-099 |
| 120 | 20 | PA | | 1-0 | 33-27-11 | D05134P | | 9 | | | | SM00006 | | 9 | | 150-154, 157-165, 167-199 |
| 120 | 20 | PQ | ET | 1-0 | 33-27-11 | D05134P | | 9 | | | | SM00006 | | 9 | | 155-156, 166 |
| 120Z | | | ET | 0-0 | 33-27-11 | D05134P | | DED | | | | SM00006 | DED | | | 155-156, 166 |
| 121 | 18 | PA | | 14-0 | 33-27-11 | L01198 | | =G | C | | | GD01114 | A.. | 2 | | 050-099 |
| 122 | 18 | PA | | 16-0 | 33-27-11 | L01197 | | =P | C | | | D05134P | 33 | | | 050-099 |
| 123 | 18 | PA | | 13-0 | 33-27-11 | L01197 | | =G | C | | | GD01114 | A.. | 2 | | 050-099 |
| 185 | 20 | PA | | 16-8 | 21-45-21 | D21200 | | 12 | | | | D21198 | 6 | | | 275-299 |
| 187 | 20 | PA | | 16-8 | 21-45-21 | D21200 | | 10 | | | | GD01114 | S.. | 2 | | 275-299 |
| 188 | 20 | PA | | 16-8 | 21-45-21 | D21200 | | 6 | | | | D21198 | 8 | | | 275-299 |
| 189 | 20 | PA | | 16-8 | 21-45-21 | D21200 | | 9 | | | | D21198 | 9 | | | 275-299 |
| 190 | 20 | PA | | 14-2 | 21-45-21 | D21200 | | 1 | | | | GD01114 | A.. | 2 | | 275-299 |
| 191 | 20 | PA | | 14-2 | 21-45-21 | D21200 | | 7 | | | | GD01114 | A.. | 2 | | 275-299 |
| 192 | 20 | PA | | 14-2 | 21-45-21 | D21200 | | 3 | | | | D21198 | 7 | | | 275-299 |
| 193 | 20 | PA | | 14-2 | 21-45-21 | D21200 | | 2 | | | | GD01114 | A.. | 2 | | 275-299 |
| 194 | 18 | PA | | 14-2 | 21-45-21 | S00940 | | =GND | D | | | GD01114 | S.. | 2 | | 275-299 |
| 304B | 18 | PC | MD | 33-4 | 21-45-21 | D05660P | | 14 | | | | D21198 | 5 | DK | | 275-299 |
| 304R | 18 | PC | MD | 0-0 | 21-45-21 | D05660P | | 12 | | | | D21198 | 3 | DK | | 275-299 |
| 304Y | 18 | PC | MD | 0-0 | 21-45-21 | D05660P | | 13 | | | | D21198 | 4 | DK | | 275-299 |
| 305B | 20 | PC | ME | 33-4 | 21-45-21 | D21200 | | 8 | | | | D21198 | 10 | | | 275-299 |
| 305R | 20 | PC | ME | 0-0 | 21-45-21 | D21200 | | 15 | | | | D21198 | 12 | | | 275-299 |
| 305Y | 20 | PC | ME | 0-0 | 21-45-21 | D21200 | | 14 | | | | D21198 | 11 | | | 275-299 |
| 501 | 20 | PA | | 14-2 | 21-45-21 | D21198 | | 2 | | | | GD01114 | S.. | 2 | | 275-299 |
| 521 | 22 | PA | | 21-0 | 33-27-11 | D13832 | | 1 | | | | D13834 | 9 | | | 162-199 |
| 522 | 22 | PA | | 21-0 | 33-27-11 | D13832 | | 2 | | | | D13834 | 10 | | | 162-199 |
| 523 | 22 | PA | | 21-0 | 33-27-11 | D13832 | | 3 | | | | D13834 | 11 | | | 162-199 |
| 524 | 22 | PA | | 21-0 | 33-27-11 | D13832 | | 4 | | | | D13834 | 12 | | | 162-199 |
| 525 | 22 | PA | | 15-0 | 33-27-11 | D05134P | | 32 | | | | D13832 | 5 | | | 162-199 |
| 527 | 20 | PA | | 23-0 | 33-27-11 | D13832 | | 7 | | | | GD04728 | A.. | E | | 162-199 |
| 528 | 20 | PA | | 13-0 | 33-27-11 | D13832 | | 8 | | | | GD02036 | S.. | E | | 162-199 |
| 529 | 22 | PA | | 21-0 | 33-27-11 | D13832 | | 9 | | | | D13834 | 1 | | | 162-199 |
| 530 | 22 | PA | | 21-0 | 33-27-11 | D13832 | | 10 | | | | D13834 | 2 | | | 162-199 |
| 531 | 22 | PA | | 21-0 | 33-27-11 | D13832 | | 11 | | | | D13834 | 3 | | | 162-199 |
| 532 | 22 | PA | | 21-0 | 33-27-11 | D13832 | | 12 | | | | D13834 | 4 | | | 162-199 |
| 535 | 22 | PA | | 13-0 | 33-27-11 | D13834 | | 5 | | | | D05134P | 33 | | | 162-199 |
| 537 | 20 | PA | | 14-0 | 33-27-11 | D13834 | | 7 | | | | GD04732 | A.. | E | | 162-199 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 24

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1228 | 286T1228 | | | P33,P37 TO P19 FEEDER (continued) | | | | | | | | | | | |
| 538 | 20 | | PA | | 14-0 | 33-27-11 | D13834 | | | | GD04736 | S.. | E | | 162-199 |
| 600 | 20 | | PA | | 13-0 | 33-27-11 | D06740J | | | | SM00006 | | | 9 | 050-099 |
| 600 | 20 | | PA | | 13-0 | 33-27-11 | SM00006 | | | 9 | D06740J | | | 8 | 150-154, 157-165, 167-199 |
| 600 | 20 | | PQ | XZ | 13-0 | 33-27-11 | SM00006 | | | 9 | D06740J | | | 8 | 155-156, 166 |
| 600Z | | | | XZ | 0-0 | 33-27-11 | SM00006 | DED | | | D06740J | DED | | | 155-156, 166 |
| 601 | 20 | | PA | | 15-0 | 33-27-11 | D06738J | | | 1 | SM00006 | | | 9 | 050-099 |
| 601 | 20 | | PA | | 14-0 | 33-27-11 | SM00006 | | | 9 | D06738J | | | 1 | 150-154, 157-165, 167-199 |
| 601 | 20 | | PQ | YA | 14-0 | 33-27-11 | SM00006 | | | 9 | D06738J | | | 1 | 155-156, 166 |
| 601Z | | | | YA | 0-0 | 33-27-11 | SM00006 | DED | | | D06738J | DED | | | 155-156, 166 |
| 602 | 20 | | PA | | 11-0 | 33-27-11 | D06738J | | | 2 | GD00938 | S.. | | 2 | 050-099 |
| 602 | 20 | | PA | | 12-0 | 33-27-11 | GD01114 | S.. | | 2 | D06738J | | | 2 | 150-199 |
| 603 | 20 | | PA | | 13-0 | 33-27-11 | D06740J | | | 1 | SM00007 | | | 9 | 050-099 |
| 603 | 20 | | PA | | 13-0 | 33-27-11 | SM00007 | | | 9 | D06740J | | | 1 | 150-154, 157-165, 167-199 |
| 603 | 20 | | PQ | YC | 13-0 | 33-27-11 | SM00007 | | | 9 | D06740J | | | 1 | 155-156, 166 |
| 603Z | | | | YC | 0-0 | 33-27-11 | SM00007 | DED | | | D06740J | DED | | | 155-156, 166 |
| 604 | 20 | | PA | | 15-0 | 33-27-11 | D06738J | | | 5 | SM00007 | | | 9 | 050-099 |
| 604 | 20 | | PA | | 14-0 | 33-27-11 | SM00007 | | | 9 | D06738J | | | 5 | 150-154, 157-165, 167-199 |
| 604 | 20 | | PQ | YD | 14-0 | 33-27-11 | SM00007 | | | 9 | D06738J | | | 5 | 155-156, 166 |
| 604Z | | | | YD | 0-0 | 33-27-11 | SM00007 | DED | | | D06738J | DED | | | 155-156, 166 |
| 605 | 20 | | PA | | 11-0 | 33-27-11 | D06738J | | | 6 | GD00938 | S.. | | 2 | 050-099 |
| 605 | 20 | | PA | | 12-0 | 33-27-11 | D06738J | | | 6 | GD01114 | S.. | | 2 | 150-199 |
| 606 | 20 | | PA | | 17-2 | 33-27-11 | D06738J | | | 7 | GD04194 | A.. | | 2 | 050-099 |
| 606 | 20 | | PA | | 12-0 | 33-27-11 | D06738J | | | 7 | GD01114 | A.. | | 2 | 150-154, 157-165, 167-199 |
| 606 | 20 | | PQ | YF | 12-0 | 33-27-11 | D06738J | | | 7 | GD01114 | A.. | | 2 | 155-156, 166 |
| 606Z | | | | YF | 0-0 | 33-27-11 | D06738J | DED | | | GD01114 | DED | | | 155-156, 166 |
| 607 | 20 | | PA | | 11-5 | 33-27-11 | D06740J | | | 3 | GD04194 | S.. | | 2 | 050-099, 150-199 |
| 608 | 20 | | PA | | 11-5 | 33-27-11 | D06740J | | | 5 | GD04194 | A.. | | 2 | 050-099, 150-154, 157-165, 167-199 |
| 608 | 20 | | PQ | YH | 11-5 | 33-27-11 | D06740J | | | 5 | GD04194 | A.. | | 2 | 155-156, 166 |
| 608Z | | | | YH | 0-0 | 33-27-11 | D06740J | DED | | | GD04194 | DED | | | 155-156, 166 |
| 609 | 20 | | PA | | 11-0 | 33-27-11 | D06738J | | | 3 | GD00938 | A.. | | 2 | 050-099 |
| 609 | 20 | | PA | | 12-0 | 33-27-11 | GD01114 | A.. | | 2 | D06738J | | | 3 | 150-154, 157-165, 167-199 |
| 609 | 20 | | PQ | YI | 12-0 | 33-27-11 | GD01114 | A.. | | 2 | D06738J | | | 3 | 155-156, 166 |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 25

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | |
|--------------|-----------------|--|----|--|----------|----------|---------|----|-----|-------|---------|-------|---------|------|--------|-------|------|---------------------------------------|
| | | | | | Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type |
| W1228 | 286T1228 | | | P33,P37 TO P19 FEEDER (continued) | | | | | | | | | | | | | | |
| 609Z | | | | YI | 0-0 | 33-27-11 | GD01114 | | DED | | | | D06738J | | DED | | | 155-156, 166 |
| 610 | 20 | | PA | | 11-0 | 33-27-11 | D06738J | | 4 | | | | GD00938 | | S.. | 2 | | 050-099 |
| 610 | 20 | | PA | | 12-0 | 33-27-11 | GD01114 | | S.. | 2 | | | D06738J | | 4 | | | 150-199 |
| 611 | 20 | | PA | | 11-0 | 33-27-11 | D06738J | | 8 | | | | GD00938 | | S.. | 2 | | 050-099 |
| 611 | 20 | | PA | | 12-0 | 33-27-11 | D06738J | | 8 | | | | GD01114 | | S.. | 2 | | 150-199 |
| 612 | 20 | | PA | | 11-5 | 33-27-11 | D06740J | | 2 | | | | GD04194 | | A.. | 2 | | 050-099, 150-154, 157-165, 167-199 |
| 612 | 20 | | PQ | YL | 11-5 | 33-27-11 | D06740J | | 2 | | | | GD04194 | | A.. | 2 | | 155-156, 166 |
| 612Z | | | | YL | 0-0 | 33-27-11 | D06740J | | DED | | | | GD04194 | | DED | | | 155-156, 166 |
| 613 | 20 | | PA | | 11-5 | 33-27-11 | D06740J | | 4 | | | | GD04194 | | S.. | 2 | | 050-099, 150-199 |
| 614 | 20 | | PA | | 11-5 | 33-27-11 | D06740J | | 6 | | | | GD04194 | | S.. | 2 | | 050-099, 150-199 |
| 615 | 20 | | PA | | 11-5 | 33-27-11 | D06740J | | 7 | | | | GD04194 | | A.. | 2 | | 050-099, 150-199 |
| 800 | 16 | | PA | | 35-0 | 38-13-11 | D05660P | | 11 | | | | D05134P | | 16 | | | 150-157 |
| 800 | 16 | | PA | | 35-0 | 38-13-11 | D05660P | | 11 | | | | D05134P | | 34 | | | 162-199 |
| A-A | | | | | 0-0 | 33-27-11 | L00202 | | BLK | | | | SP01226 | | 9 | | | ALL |
| A-B | | | | | 0-0 | 33-27-11 | L00202 | | BLK | | | | SP01228 | | 9 | | | ALL |
| A-C | | | | | 0-0 | 33-27-11 | L00202 | | WHT | | | | SP01230 | | 9 | | | ALL |
| A-D | | | | | 0-0 | 33-27-11 | L00202 | | WHT | | | | SP01232 | | 9 | | | ALL |
| B-A | | | | | 0-0 | 33-27-11 | L00201 | | BLK | | | | SP01234 | | 9 | | | ALL |
| B-B | | | | | 0-0 | 33-27-11 | L00201 | | BLK | | | | SP01236 | | 9 | | | ALL |
| B-C | | | | | 0-0 | 33-27-11 | L00201 | | WHT | | | | SP01238 | | 9 | | | ALL |
| B-D | | | | | 0-0 | 33-27-11 | L00201 | | WHT | | | | SP01240 | | 9 | | | ALL |
| C-A | | | | | 0-0 | 33-22-41 | L00213 | | BLK | | | | SP01114 | | 9 | | | ALL |
| C-B | | | | | 0-0 | 33-22-41 | L00213 | | BLK | | | | SP01116 | | 9 | | | ALL |
| C-C | | | | | 0-0 | 33-22-41 | L00213 | | WHT | | | | SP01118 | | 9 | | | ALL |
| C-D | | | | | 0-0 | 33-22-41 | L00213 | | WHT | | | | SP01120 | | 9 | | | ALL |
| D-A | | | | | 0-0 | 33-22-11 | L00191 | | BLK | | | | SP01456 | | 9 | | | ALL |
| D-B | | | | | 0-0 | 33-22-11 | L00191 | | BLK | | | | SP01458 | | 9 | | | ALL |
| D-C | | | | | 0-0 | 33-22-11 | L00191 | | WHT | | | | SP01460 | | 9 | | | ALL |
| D-D | | | | | 0-0 | 33-22-11 | L00191 | | WHT | | | | SP01462 | | 9 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1220

Page 26 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | 286T1230 | | | AC FEEDER CLOSET LT,ATT WORK LTS | | | | | | | | | | | |
| 001 | 22 | | PA | | 44-0 | 33-22-21 | D05172P | | | | SM00001 | | | S | 050-099 |
| 001 | 20 | | PA | | 43-0 | 33-22-21 | D05172P | | | | SM00001 | | | S | 150-199 |
| 001 | 22 | | PA | | 51-0 | 33-22-21 | D05172P | | | | D06388J | = 1 | | | 275-278 |
| 001 | 22 | | PA | | 31-0 | 33-22-21 | D05172P | | | | SM00001 | | | S | 280-299 |
| 003 | 22 | | PA | | 25-0 | 33-22-21 | SM00001 | | S | | D05720J | = 1 | | | 050-099 |
| 005 | 20 | | PA | | 15-0 | 33-22-21 | D05722P | | | = 1 | GD01920 | A.. | 2 | | 050-099 |
| 007 | 20 | | PA | | 6-0 | 33-22-31 | GD00119 | | | A.. | D11872 | | 2 | | 050-099, 150-199 |
| 007 | 20 | | PA | | 17-0 | 33-22-31 | GD01114 | | | A.. | L00185 | = G | C | | 275-299 |
| 008 | 20 | | PA | | 6-0 | 33-22-31 | D11872 | | | | GD00119 | A.. | 2 | | 050-099, 150-199 |
| 008 | 20 | | PA | | 5-0 | 33-22-31 | L00185 | | | = G | L00190 | = G | C | | 275-299 |
| 009 | 20 | | PA | | 20-0 | 33-22-31 | D05170P | | | | L00185 | = P | C | * | 275-299 |
| 010 | 20 | | PA | | 5-0 | 33-22-31 | L00190 | | | = P | L00185 | = P | C | * | 275-299 |
| 014 | 22 | | PA | | 43-0 | 33-22-41 | D05172P | | | | D05170P | | 14 | | 050-099 |
| 014 | 22 | | PA | | 44-0 | 33-22-41 | D05172P | | | | D05170P | | 14 | | 150-199, 275-299 |
| 016 | 20 | | PA | | 43-0 | 33-22-42 | D05172P | | | | D05170P | | 16 | | 050-099 |
| 016 | 20 | | PA | | 44-0 | 33-22-42 | D05172P | | | | D05170P | | 16 | | 150-199, 275-299 |
| 017 | 20 | | PA | | 43-0 | 33-22-11 | D05172P | | | | D05170P | | 4 | | 050-099 |
| 017 | 20 | | PA | | 44-0 | 33-22-11 | D05172P | | | | D05170P | | 4 | | 150-154, 275-299 |
| 017 | 16 | | PA | | 44-0 | 33-22-11 | D05172P | | FL | | D05170P | | 4 | FM | 155-199 |
| 018 | 20 | | PA | | 43-0 | 33-22-11 | D05172P | | | | D05170P | | 5 | | 050-099 |
| 018 | 20 | | PA | | 44-0 | 33-22-11 | D05172P | | | | D05170P | | 5 | | 150-199, 275-299 |
| 020 | 20 | | PA | | 7-0 | 33-22-11 | L00183 | | | = G | GD01114 | A.. | 2 | | ALL |
| 021 | 20 | | PA | | 24-0 | 33-22-11 | D05170P | | | | L00183 | = P | C | | 050-099, 150-157, 275-299 |
| 021 | 20 | | PA | | 23-0 | 33-22-11 | D05170P | | | | L00183 | = P | C | | 162-199 |
| 023 | 22 | | PA | | 43-0 | 33-51-11 | D05172P | | | | D05170P | | 12 | | 050-099 |
| 023 | 22 | | PA | | 44-0 | 33-51-11 | D05172P | | | | D05170P | | 12 | | 150-199, 275-299 |
| 024 | 24 | | PK | | 43-0 | 33-21-31 | D05172P | | | | D05170P | | 6 | | 050-099 |
| 024 | 24 | | PK | | 44-0 | 33-21-31 | D05172P | | | | D05170P | | 6 | | 150-199, 275-299 |
| 025 | 18 | | PA | | 43-0 | 33-24-11 | D05172P | | DL | | D05170P | | 19 | DK | 050-099 |
| 025 | 16 | | PA | | 1-0 | 33-24-11 | D05172P | | FL | | SM00007 | | 9 | | 150-199, 275-299 |
| 026 | 18 | | PA | | 43-0 | 33-24-11 | D05172P | | DL | | D05170P | | 20 | DK | 050-099 |
| 026 | 16 | | PA | | 1-0 | 33-24-11 | D05172P | | FL | | SM00006 | | 9 | | 150-199, 275-299 |
| 027 | 18 | | PA | | 43-0 | 33-24-11 | D05172P | | DL | | D05170P | | 21 | DK | 050-099 |
| 027 | 16 | | PA | | 1-0 | 33-24-11 | D05172P | | FL | | SM00008 | | 9 | | 150-199, 275-299 |
| 029 | 20 | | PA | | 13-0 | 33-24-11 | D00168 | | | | GD00119 | D.. | 2 | | ALL |
| 030 | 24 | | PK | | 5-0 | 33-24-11 | D00168 | | | | D05170P | | 23 | | 050-099, 150-157, 275-299 |
| 030 | 24 | | PK | | 4-0 | 33-24-11 | D00168 | | | | D05170P | | 23 | | 162-199 |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1230 | 286T1230 | | | AC FEEDER CLOSET LT, ATT WORK LTS (continued) | | | | | | | | | | | | | |
| 042 | 24 | | PK | 43-0 | 33-21-11 | D05170P | | 1 | | | | | D05172P | 10 | | | 050-099 |
| 042 | 24 | | PK | 44-0 | 33-21-11 | D05170P | | 1 | | | | | D05172P | 10 | | | 150-199, 275-299 |
| 045 | 22 | | PA | 18-0 | 33-27-11 | SP00720 | | | 9 | | | | D05170P | 32 | | | 275-299 |
| 047 | 22 | | PA | 18-0 | 33-27-11 | SP00724 | | | 9 | | | | D05170P | 33 | | | 275-299 |
| 048 | 20 | | PA | 43-0 | 33-27-11 | D05172P | | 2 | | | | | D05170P | 31 | | | 050-099 |
| 048 | 20 | | PA | 44-0 | 33-27-11 | D05172P | | 2 | | | | | D05170P | 31 | | | 150-199, 275-299 |
| 050 | 22 | | PA | 43-0 | 52-11-11 | D05172P | | 19 | | | | | D05170P | 28 | | | 050-099 |
| 050 | 22 | | PA | 44-0 | 52-11-11 | D05172P | | 19 | | | | | D05170P | 28 | | | 150-199, 275-299 |
| 051 | 22 | | PA | 43-0 | 52-11-11 | D05172P | | 20 | | | | | D05170P | 29 | | | 050-099 |
| 051 | 22 | | PA | 44-0 | 52-11-11 | D05172P | | 20 | | | | | D05170P | 29 | | | 150-199, 275-299 |
| 052 | 22 | | PA | 43-0 | 52-11-11 | D05172P | | 21 | | | | | D05170P | 30 | | | 050-099 |
| 052 | 22 | | PA | 44-0 | 52-11-11 | D05172P | | 21 | | | | | D05170P | 30 | | | 150-199, 275-299 |
| 053 | 22 | | PA | 11-0 | 33-22-21 | SM00001 | | | | S | | | D05170P | 15 | | | 050-099 |
| 053 | 22 | | PA | 11-0 | 33-22-21 | D05170P | | 15 | | | | | SM00001 | | | S | 150-157 |
| 053 | 22 | | PA | 12-0 | 33-22-21 | D05170P | | 15 | | | | | SM00001 | | | S | 162-199 |
| 053 | 22 | | PA | 15-0 | 33-22-21 | D05170P | | 15 | | | | | SM00001 | | | S | 280-299 |
| 056 | 20 | | PA | 27-0 | 33-24-14 | SP03140 | | | 9 | | | | D05170P | 35 | | | 275-299 |
| 057 | 20 | | PA | 27-0 | 33-24-14 | SP03138 | | | 9 | | | | D05170P | 36 | | | 275-299 |
| 062 | 20 | | PA | 14-0 | 33-22-31 | D05170P | | 8 | | | | | D11872 | 1 | | | 050-099 |
| 062 | 20 | | PA | 16-0 | 33-22-31 | D11872 | | 1 | | | | | D05170P | 8 | | | 150-157 |
| 062 | 20 | | PA | 14-0 | 33-22-31 | D11872 | | 1 | | | | | D05170P | 8 | | | 162-199 |
| 065 | 20 | | PA | 42-0 | 33-24-11 | D05172P | | 3 | | | | | D05170P | 22 | | | 050-099 |
| 065 | 20 | | PA | 44-0 | 33-24-11 | D05172P | | 3 | | | | | D05170P | 22 | | | 150-199, 275-299 |
| 067 | 20 | | PA | 3-0 | 33-22-21 | D06386P | | =1 | | | | | GD00434 | A.. | 2 | | 150-154 |
| 067 | 20 | | PA | 5-0 | 33-22-21 | D06386P | | =1 | | | | | GD00434 | A.. | 2 | | 155-157 |
| 067 | 20 | | PA | 10-0 | 33-22-21 | D06386P | | =1 | | | | | GD00119 | A.. | 2 | | 275-299 |
| 068 | 22 | | PA | 15-0 | 33-22-21 | D06388J | | =1 | | | | | SM00001 | | | S | 150-157 |
| 068 | 22 | | PA | 21-0 | 33-22-21 | D06388J | | =1 | | | | | SM00001 | | | S | 280-299 |
| 081 | 12 | | PA | 43-0 | 33-24-11 | SM00006 | | | 9 | | | | SM00009 | | | S | 150-157, 275-299 |
| 081 | 12 | | PA | 42-4 | 33-24-11 | SM00006 | | | 9 | | | | SM00009 | | | S | 162-199 |
| 082 | 12 | | PA | 43-0 | 33-24-11 | SM00007 | | | 9 | | | | SM00010 | | | S | 150-157, 275-299 |
| 082 | 12 | | PA | 42-4 | 33-24-11 | SM00007 | | | 9 | | | | SM00010 | | | S | 162-199 |
| 083 | 12 | | PA | 43-0 | 33-24-11 | SM00008 | | | 9 | | | | SM00011 | | | S | 150-157, 275-299 |
| 083 | 12 | | PA | 42-4 | 33-24-11 | SM00008 | | | 9 | | | | SM00011 | | | S | 162-199 |
| 084 | 16 | | PA | 1-0 | 33-24-11 | D05170P | | 20 | FM | | | | SM00009 | | | S | 150-199, 275-299 |
| 085 | 16 | | PA | 1-0 | 33-24-11 | D05170P | | 19 | FM | | | | SM00010 | | | S | 150-199, 275-299 |
| 086 | 16 | | PA | 1-0 | 33-24-11 | D05170P | | 21 | FM | | | | SM00011 | | | S | 150-199, 275-299 |
| 089 | 22 | | PK | 20-0 | 30-46-11 | D05170P | | 13 | | | | | D06604P | | 1 | | ALL |
| 090 | 20 | | PK | 12-0 | 30-46-11 | D06604P | | 2 | | | | | GD04194 | | D.. | 2 | 050-099, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | 286T1230 | | | AC FEEDER CLOSET LT,ATT WORK LTS (continued) | | | | | | | | | | | | |
| 090 | 20 | | PK | | 11-0 | 30-46-11 | D06604P | | 2 | | | GD00119 | D.. | 2 | | 150-199 |
| 091 | 20 | | PK | | 12-0 | 30-46-11 | D06604P | | 3 | | | GD04194 | S.. | 2 | | 050-099, 275-299 |
| 091 | 20 | | PK | | 11-0 | 30-46-11 | D06604P | | 3 | | | GD00119 | S.. | 2 | | 150-199 |
| 103 | 22 | | PA | | 5-0 | 33-22-41 | SP03984 | | | 9 | | D05170P | | 32 | | 150-157 |
| 103 | 22 | | PA | | 7-0 | 33-22-41 | SP03984 | | | 9 | | D05170P | | 32 | | 162-199 |
| 104 | 20 | | PA | | 4-0 | 35-21-14 | D08706J | | | 1 | | D05170P | | 55 | | 050-099 |
| 104 | 20 | | PA | | 4-0 | 35-21-14 | D05170P | | | 55 | | D08706J | | 1 | | 162-199 |
| 105 | 20 | | PA | | 4-0 | 33-51-13 | D05170P | | | 52 | | D08706J | | 7 | | 050-099, 162-199 |
| 106 | 22 | | PA | | 4-0 | 33-22-33 | D05170P | | | 54 | | D08706J | | 6 | | 050-099, 162-199 |
| 116 | 22 | | PA | | 4-0 | 33-24-13 | D08706J | | | 12 | | D05170P | | 36 | | 050-099, 162-199 |
| 117 | 22 | | PA | | 4-0 | 33-24-13 | D08706J | | | 13 | | D05170P | | 35 | | 050-099, 162-199 |
| 118 | 20 | | PA | | 4-0 | 26-13-12 | D05170P | | | 43 | | D08706J | | 3 | | 050-099, 162-163 |
| 118 | 20 | | PA | | 12-0 | 26-13-12 | SM00020 | | | | S | D08706J | | 3 | | 164-199 |
| 119 | 20 | | PA | | 4-0 | 26-13-12 | D05170P | | | 44 | | D08706J | | 14 | | 050-099 |
| 119 | 20 | | PA | | 12-0 | 26-13-12 | D08706J | | | 14 | | SM00019 | | | S | 164-199 |
| 120 | 20 | | PA | | 4-0 | 26-13-12 | D05170P | | | 45 | | D08706J | | 5 | | 050-099 |
| 120 | 20 | | PA | | 4-0 | 26-13-12 | D08706J | | | 5 | | D05170P | | 45 | | 162-199 |
| 121 | 20 | | PA | | 6-0 | 33-22-31 | D11872 | | | 4 | | GD00119 | A.. | 2 | | 050-099, 153-199 |
| 122 | 20 | | PA | | 6-0 | 33-22-31 | D11872 | | | 5 | | GD00119 | A.. | 2 | | 050-099, 153-199 |
| 123 | 20 | | PA | | 11-0 | 33-27-11 | D13836 | | | 1 | | SM00001 | | | S | 162-199 |
| 124 | 20 | | PA | | 34-0 | 33-27-11 | D13836 | | | 2 | | GD01918 | A.. | 2 | | 162-199 |
| 125 | 20 | | PA | | 4-0 | 26-13-12 | D05170P | | | 44 | | D08706J | | 14 | | 162-163 |
| 126 | 20 | | PA | | 4-0 | 26-13-12 | D08706J | | | 15 | | D05170P | | 47 | | 050-099 |
| 126 | 20 | | PA | | 4-0 | 26-13-12 | D05170P | | | 47 | | D08706J | | 15 | | 162-163 |
| 126 | 20 | | PA | | 12-0 | 26-13-12 | D05170P | | | 47 | | D08706J | | 15 | | 164-199 |
| 127 | 20 | | PA | | 6-0 | 26-13-12 | D13966 | | | = 1 | | SM00019 | | | S | 164-199 |
| 128 | 20 | | PA | | 6-0 | 26-13-12 | D13968 | | | = 1 | | SM00020 | | | S | 164-199 |
| 130 | 20 | | PA | | 12-0 | 26-13-12 | D05170P | | | 44 | | SM00019 | | | S | 164-199 |
| 131 | 20 | | PA | | 12-0 | 26-13-12 | D05170P | | | 43 | | SM00020 | | | S | 164-199 |
| 138 | 20 | | PA | | 18-0 | 33-24-13 | D05170P | | | 37 | | SP02206 | | 9 | | 280-299 |
| 139 | 20 | | PA | | 18-0 | 33-24-13 | D05170P | | | 38 | | SP02208 | | 9 | | 280-299 |
| 202B | 22 | | PB | B | 12-0 | 23-31-14 | B00070 | COM | Z | | | SM00014 | | | S | 050-099 |
| 202B | 22 | | PB | IB | 13-0 | 23-31-14 | B00070 | COM | Z | | | SM00014 | | 9 | | 150-157 |
| 202B | 22 | | PB | IB | 12-0 | 23-31-14 | B00070 | COM | Z | | | SM00014 | | 9 | | 162-199 |
| 202B | 22 | | PB | B | 22-0 | 23-31-14 | B00070 | COM | Z | | | D05170P | | 18 | | 275-299 |
| 202R | 22 | | PB | B | 0-0 | 23-31-14 | SM00013 | | | | S | B00070 | | 2K | Z | 050-099 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-14 | B00070 | | | 2K | Z | SM00013 | | 9 | | 150-199 |
| 202R | 22 | | PB | B | 0-0 | 23-31-14 | B00070 | | | 2K | Z | D05170P | | 17 | | 275-299 |
| 203B | 22 | | PB | IC | 13-0 | 23-31-14 | B00292 | COM | Z | | | SM00014 | | | S | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1230 | 286T1230 | | | AC FEEDER CLOSET LT, ATT WORK LTS (continued) | | | | | | | | | | | | |
| 203B | 22 | | PB | IC | 13-0 | 23-31-14 | B00292 | COM | Z | | SM00014 | | 9 | | 150-157 | |
| 203B | 22 | | PB | IC | 15-0 | 23-31-14 | B00292 | COM | Z | | SM00014 | | 9 | | 162-199 | |
| 203R | 22 | | PB | IC | 0-0 | 23-31-14 | B00292 | 4K | Z | | SM00013 | | S | | 050-099 | |
| 203R | 22 | | PB | IC | 0-0 | 23-31-14 | B00292 | 4K | Z | | SM00013 | | 9 | | 150-199 | |
| 204B | 22 | | PB | ID | 11-0 | 23-31-14 | D05170P | | 18 | | SM00014 | | S | | 050-099 | |
| 204B | 22 | | PB | ID | 11-0 | 23-31-14 | D05170P | | 18 | | SM00014 | | 9 | | 150-157 | |
| 204B | 22 | | PB | ID | 12-0 | 23-31-14 | D05170P | | 18 | | SM00014 | | 9 | | 162-199 | |
| 204R | 22 | | PB | ID | 0-0 | 23-31-14 | D05170P | | 17 | | SM00013 | | S | | 050-099 | |
| 204R | 22 | | PB | ID | 0-0 | 23-31-14 | D05170P | | 17 | | SM00013 | | 9 | | 150-199 | |
| 205B | 22 | | PB | IE | 41-0 | 21-66-11 | D13878 | | 1 | | SP04090 | | S | | 050-099 | |
| 205B | 22 | | PB | IE | 44-0 | 21-66-11 | D13878 | | 1 | | SP04090 | | S | | 162-199 | |
| 205R | 22 | | PB | IE | 0-0 | 21-66-11 | D13878 | | 2 | | SP04092 | | S | | 050-099, 162-199 | |
| 206B | 22 | | PB | IF | 23-0 | 21-66-11 | D13878 | | 3 | | D13868 | | 1 | | 050-099 | |
| 206B | 22 | | PB | IF | 25-0 | 21-66-11 | D13878 | | 3 | | D13868 | | 1 | | 162-199 | |
| 206R | 22 | | PB | IF | 0-0 | 21-66-11 | D13878 | | 4 | | D13868 | | 3 | | 050-099, 162-199 | |
| 207B | 22 | | PB | IG | 15-0 | 21-66-11 | D13878 | | 5 | | D08706J | | 10 | | 050-099 | |
| 207B | 22 | | PB | IG | 16-0 | 21-66-11 | D13878 | | 5 | | D08706J | | 10 | | 162-199 | |
| 207R | 22 | | PB | IG | 0-0 | 21-66-11 | D13878 | | 6 | | D08706J | | 11 | | 050-099, 162-199 | |
| 301B | 22 | | PC | MA | 15-0 | 21-66-11 | D13878 | | 8 | | D08706J | | 24 | | 050-099 | |
| 301B | 22 | | PC | MA | 16-0 | 21-66-11 | D13878 | | 8 | | D08706J | | 24 | | 162-199 | |
| 301R | 22 | | PC | MA | 0-0 | 21-66-11 | D13878 | | 9 | | D08706J | | 25 | | 050-099, 162-199 | |
| 301Y | 22 | | PC | MA | 0-0 | 21-66-11 | D13878 | | 10 | | D08706J | | 26 | | 050-099, 162-199 | |
| 501 | 20 | | PA | | 4-0 | 33-26-21 | D05170P | | 46 | | D08706J | | 4 | | 050-099, 162-199 | |
| 502 | 22 | | PQ | UB | 27-0 | 21-66-11 | D13878 | | 18 | | D06936P | | 1 | | 050-099 | |
| 502 | 22 | | PQ | UB | 29-0 | 21-66-11 | D13878 | | 18 | | D06936P | | 1 | | 162-199 | |
| 502Z | | | | UB | 0-0 | 21-66-11 | D13878 | | DED | | D06936P | | DED | | 050-099, 162-199 | |
| 503 | 22 | | PA | | 14-0 | 21-66-11 | D13878 | | 40 | | D05170P | | 37 | | 050-099 | |
| 503 | 22 | | PA | | 15-0 | 21-66-11 | D13878 | | 40 | | D05170P | | 37 | | 162-199 | |
| 504 | 22 | | PQ | UD | 27-0 | 21-66-11 | D13878 | | 31 | | D06936P | | 2 | | 050-099 | |
| 504 | 22 | | PQ | UD | 29-0 | 21-66-11 | D13878 | | 31 | | D06936P | | 2 | | 162-199 | |
| 504Z | | | | UD | 0-0 | 21-66-11 | D13878 | | DED | | D06936P | | DED | | 050-099, 162-199 | |
| 506 | 20 | | PA | | 5-0 | 21-66-11 | D13878 | | 60 | | GD01916 | | S.. | 2 | 050-099 | |
| 506 | 20 | | PA | | 5-0 | 21-66-11 | GD01916 | | S.. | 2 | D13878 | | 60 | | 162-199 | |
| 507 | 20 | | PA | | 27-0 | 21-66-11 | D13878 | | 13 | | GD01916 | | D.. | 2 | 050-099 | |
| 507 | 20 | | PA | | 5-0 | 21-66-11 | D13878 | | 13 | | GD01916 | | D.. | 2 | 162-199 | |
| 508 | 22 | | PQ | UH | 27-0 | 21-66-11 | D13878 | | 32 | | D06936P | | 3 | | 050-099 | |
| 508 | 22 | | PQ | UH | 29-0 | 21-66-11 | D13878 | | 32 | | D06936P | | 3 | | 162-199 | |
| 508Z | | | | UH | 0-0 | 21-66-11 | D13878 | | DED | | D06936P | | DED | | 050-099, 162-199 | |
| 509 | 22 | | PQ | UI | 27-0 | 21-66-11 | D13878 | | 33 | | D06936P | | 4 | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | 286T1230 | | | AC FEEDER CLOSET LT,ATT WORK LTS (continued) | | | | | | | | | | | |
| 509 | 22 | PQ | UI | 29-0 | 21-66-11 | D13878 | | 33 | | D06936P | | 4 | | 162-199 | |
| 509Z | | | UI | 0-0 | 21-66-11 | D13878 | | DED | | D06936P | | DED | | 050-099, 162-199 | |
| 510 | 22 | PQ | UJ | 10-0 | 21-66-11 | D13878 | | 38 | | D06936P | | 5 | | 050-099 | |
| 510 | 22 | PQ | UJ | 29-0 | 21-66-11 | D13878 | | 38 | | D06936P | | 5 | | 162-199 | |
| 510Z | | | UJ | 0-0 | 21-66-11 | D13878 | | DED | | D06936P | | DED | | 050-099, 162-199 | |
| 511 | 22 | PA | | 14-0 | 21-66-11 | D13878 | | 29 | | D05170P | | 38 | | 050-099 | |
| 511 | 22 | PA | | 15-0 | 21-66-11 | D13878 | | 29 | | D05170P | | 38 | | 162-199 | |
| 512 | 22 | PA | | 14-0 | 21-66-11 | D13878 | | 28 | | D05170P | | 39 | | 050-099 | |
| 512 | 22 | PA | | 15-0 | 21-66-11 | D13878 | | 28 | | D05170P | | 39 | | 162-199 | |
| 513 | 22 | PA | | 14-0 | 21-66-11 | D13878 | | 27 | | D05170P | | 40 | | 050-099 | |
| 513 | 22 | PA | | 15-0 | 21-66-11 | D13878 | | 27 | | D05170P | | 40 | | 162-199 | |
| 514 | 22 | PA | | 15-0 | 21-66-11 | D13878 | | 23 | | D08706J | | 16 | | 050-099 | |
| 514 | 22 | PA | | 16-0 | 21-66-11 | D13878 | | 23 | | D08706J | | 16 | | 162-199 | |
| 515 | 22 | PA | | 15-0 | 21-66-11 | D13878 | | 24 | | D08706J | | 17 | | 050-099 | |
| 515 | 22 | PA | | 16-0 | 21-66-11 | D13878 | | 24 | | D08706J | | 17 | | 162-199 | |
| 516 | 22 | PQ | UP | 27-0 | 21-66-11 | D13878 | | 20 | | D06936P | | 8 | | 050-099 | |
| 516 | 22 | PQ | UP | 29-0 | 21-66-11 | D13878 | | 20 | | D06936P | | 8 | | 162-199 | |
| 516Z | | | UP | 0-0 | 21-66-11 | D13878 | | DED | | D06936P | | DED | | 050-099, 162-199 | |
| 517 | 22 | PQ | UQ | 27-0 | 21-66-11 | D13878 | | 21 | | D06936P | | 9 | | 050-099 | |
| 517 | 22 | PQ | UQ | 29-0 | 21-66-11 | D13878 | | 21 | | D06936P | | 9 | | 162-199 | |
| 517Z | | | UQ | 0-0 | 21-66-11 | D13878 | | DED | | D06936P | | DED | | 050-099, 162-199 | |
| 519 | 22 | PQ | US | 27-0 | 21-66-11 | D13878 | | 25 | | D06936P | | 10 | | 050-099 | |
| 519 | 22 | PQ | US | 29-0 | 21-66-11 | D13878 | | 25 | | D06936P | | 10 | | 162-199 | |
| 519Z | | | US | 0-0 | 21-66-11 | D13878 | | DED | | D06936P | | DED | | 050-099, 162-199 | |
| 520 | 22 | PQ | UT | 27-0 | 21-66-11 | D13878 | | 22 | | D06936P | | 11 | | 050-099 | |
| 520 | 22 | PQ | UT | 29-0 | 21-66-11 | D13878 | | 22 | | D06936P | | 11 | | 162-199 | |
| 520Z | | | UT | 0-0 | 21-66-11 | D13878 | | DED | | D06936P | | DED | | 050-099, 162-199 | |
| 521 | 22 | PA | | 1-0 | 21-66-11 | D13878 | | 45 | | D13878 | | 50 | | 050-099, 162-199 | |
| 522 | 22 | PQ | UV | 18-0 | 21-66-11 | D08706J | | 8 | | D06936P | | 6 | | 050-099 | |
| 522 | 22 | PQ | UV | 18-0 | 21-66-11 | D06936P | | 6 | | D08706J | | 8 | | 162-199 | |
| 522Z | | | UV | 0-0 | 21-66-11 | D08706J | | DED | | D06936P | | DED | | 050-099 | |
| 522Z | | | UV | 0-0 | 21-66-11 | D06936P | | DED | | D08706J | | DED | | 162-199 | |
| 523 | 22 | PQ | UW | 18-0 | 21-66-11 | D08706J | | 9 | | D06936P | | 7 | | 050-099 | |
| 523 | 22 | PQ | UW | 18-0 | 21-66-11 | D06936P | | 7 | | D08706J | | 9 | | 162-199 | |
| 523Z | | | UW | 0-0 | 21-66-11 | D08706J | | DED | | D06936P | | DED | | 050-099 | |
| 523Z | | | UW | 0-0 | 21-66-11 | D06936P | | DED | | D08706J | | DED | | 162-199 | |
| 524 | 22 | PA | | 14-0 | 21-66-11 | D13878 | | 39 | | D05170P | | 41 | | 050-099 | |
| 524 | 22 | PA | | 15-0 | 21-66-11 | D05170P | | 41 | | D13878 | | 39 | | 162-199 | |
| 525 | 22 | PA | | 4-0 | 21-66-11 | D08706J | | 28 | | D05170P | | 48 | | 050-099, 162-199 | |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1230 | 286T1230 | | | AC FEEDER CLOSET LT, ATT WORK LTS (continued) | | | | | | | | | | | | | |
| 526 | 20 | | PA | 4-0 | 26-13-12 | D08706J | | 18 | | | | | D05170P | 27 | | | 050-099, 162-199 |
| 601 | 20 | | PA | 16-0 | 33-24-13 | D05170P | | 33 | | | | | L01069 | 1 | C | | 050-099 |
| 601 | 20 | | PA | 16-0 | 33-24-13 | L01069 | | 1 | C | | | | D05170P | 33 | | | 150-199 |
| 602 | 20 | | PA | 16-0 | 33-24-13 | D05170P | | 34 | | | | | L01069 | 3 | C | | 050-099 |
| 602 | 20 | | PA | 16-0 | 33-24-13 | L01069 | | 3 | C | | | | D05170P | 34 | | | 150-199 |
| 603 | 20 | | PA | 9-0 | 33-24-13 | GD00119 | | A.. | 2 | | | | L01069 | 2 | C | | 050-099 |
| 603 | 20 | | PA | 8-0 | 33-24-13 | L01069 | | 2 | C | | | | GD00119 | A.. | 2 | | 150-199 |
| 604 | 20 | | PA | 18-0 | 33-24-14 | D05170P | | 10 | | | | | SP03902 | | S | | 050-099, 162-199 |
| 604 | 20 | | PA | 37-0 | 33-24-14 | D05170P | | 10 | | | | | SP03902 | | S | | 150-157 |
| 605 | 20 | | PA | 18-0 | 33-24-14 | D05170P | | 9 | | | | | SP03904 | | S | | 050-099, 162-199 |
| 605 | 20 | | PA | 37-0 | 33-24-14 | D05170P | | 9 | | | | | SP03904 | | S | | 150-157 |
| 814 | 22 | | PA | 42-0 | SPARE | D05172P | | 11 | | | | | D05170P | 11 | | | 050-099 |
| 814 | 22 | | PA | 44-0 | SPARE | D05172P | | 11 | | | | | D05170P | 11 | | | 150-199, 275-299 |
| 815 | 22 | | PA | 43-0 | SPARE | D05172P | | 17 | | | | | D05170P | 26 | | | 050-099 |
| 815 | 22 | | PA | 44-0 | SPARE | D05172P | | 17 | | | | | D05170P | 26 | | | 150-199, 275-299 |
| 816 | 20 | | PA | 44-0 | SPARE | D05172P | | 18 | | | | | D05170P | 27 | | | 150-157, 275-299 |
| A-B | | | | 0-0 | 21-66-11 | TS0523 | | 1 | | | | | SP04090 | | S | | 050-099 |
| A-B | | | | 0-0 | 21-66-11 | SP04090 | | | S | | | | TS0523 | 1 | | | 162-199 |
| B-A | | | | 0-0 | 21-66-11 | TS0523 | | 2 | | | | | SP04092 | | S | | 050-099 |
| B-A | | | | 0-0 | 21-66-11 | SP04092 | | | S | | | | TS0523 | 2 | | | 162-199 |
| W1232 | 286T1232 | | | P36 TO P19 AC FEEDER | | | | | | | | | | | | | |
| 001 | 20 | | PA | 35-4 | 25-42-11 | D05100P | | 1 | | | | | D04282P | 1 | | | 050-099 |
| 001 | 18 | | PA | 35-10 | 25-42-11 | D05100P | | 1 | | | | | D04282P | 1 | | | 150-157, 275-278 |
| 001 | 18 | | PA | 35-4 | 25-42-11 | D05100P | | 1 | | | | | D04282P | 1 | | | 162-199 |
| 001 | 18 | | PA | 35-11 | 25-42-11 | D05100P | | 1 | | | | | D04282P | 1 | | | 280-299 |
| 006 | 16 | | PA | 35-4 | 38-13-11 | D05100P | | 7 | | | | | D04282P | 7 | | | 050-099, 162-199 |
| 006 | 16 | | PA | 35-10 | 38-13-11 | D05100P | | 7 | | | | | D04282P | 7 | | | 150-157, 275-278 |
| 006 | 16 | | PA | 35-11 | 38-13-11 | D05100P | | 7 | | | | | D04282P | 7 | | | 280-299 |
| 008 | 18 | | PA | 35-4 | 21-24-11 | D04282P | | 4 | | | | | D05100P | 4 | | | 050-099 |
| 008 | 18 | | PA | 35-10 | 21-24-11 | D05100P | | 4 | | | | | D04282P | 4 | | | 150-157 |
| 008 | 18 | | PA | 35-4 | 21-24-11 | D05100P | | 4 | | | | | D04282P | 4 | | | 162-199 |
| 009 | 18 | | PA | 35-4 | 21-24-11 | D04282P | | 6 | | | | | D05100P | 6 | | | 050-099 |
| 009 | 18 | | PA | 35-10 | 21-24-11 | D05100P | | 6 | | | | | D04282P | 6 | | | 150-157 |
| 009 | 18 | | PA | 35-4 | 21-24-11 | D05100P | | 6 | | | | | D04282P | 6 | | | 162-199 |
| 010 | 18 | | PA | 35-4 | 21-24-11 | D04282P | | 8 | | | | | D05100P | 8 | | | 050-099 |
| 010 | 18 | | PA | 35-10 | 21-24-11 | D05100P | | 8 | | | | | D04282P | 8 | | | 150-157 |
| 010 | 18 | | PA | 35-4 | 21-24-11 | D05100P | | 8 | | | | | D04282P | 8 | | | 162-199 |
| 016 | 18 | | PA | 35-4 | 38-32-12 | D05100P | | 5 | | | | | D04282P | 5 | | | 050-099, 162-165 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1232 | 286T1232 | | | P36 TO P19 AC FEEDER (continued) | | | | | | | | | | | |
| 016 | 18 | | PA | 35-10 | 38-32-12 | D05100P | | 5 | | D04282P | | 5 | | | 150-156, 275-276 |
| 100 | 22 | | PA | 44-1 | 21-66-11 | D06934P | | 1 | | D06936J | | 1 | | | 050-099 |
| 100 | 22 | | PA | 44-0 | 21-66-11 | D06934P | | 1 | | D06936J | | 1 | | | 162-199 |
| 101 | 22 | | PA | 44-1 | 21-66-11 | D06934P | | 5 | | D06936J | | 2 | | | 050-099 |
| 101 | 22 | | PA | 44-0 | 21-66-11 | D06934P | | 5 | | D06936J | | 2 | | | 162-199 |
| 102 | 20 | | PA | 4-4 | 21-66-11 | D13870 | | 3 | | GD01916 | S.. | 2 | | | 050-099 |
| 102 | 20 | | PA | 4-2 | 21-66-11 | D13870 | | 3 | | GD01916 | S.. | 2 | | | 162-199 |
| 103 | 20 | | PA | 5-3 | 21-66-11 | D13872 | | 4 | | GD01920 | D.. | 2 | | | 050-099 |
| 103 | 20 | | PA | 5-2 | 21-66-11 | D13872 | | 4 | | GD01920 | D.. | 2 | | | 162-199 |
| 104 | 20 | | PA | 5-3 | 21-66-11 | D13872 | | 7 | | GD01920 | D.. | 2 | | | 050-099 |
| 104 | 20 | | PA | 5-2 | 21-66-11 | D13872 | | 7 | | GD01920 | D.. | 2 | | | 162-199 |
| 105 | 22 | | PA | 19-6 | 21-66-11 | D13874 | | 14 | | D13872 | | 2 | | | 050-099, 162-199 |
| 106 | 20 | | PA | 3-9 | 21-66-11 | D13874 | | 8 | | GD01916 | A.. | 2 | | | 050-099, 162-199 |
| 107 | 22 | | PA | 19-6 | 21-66-11 | D13874 | | 13 | | D13872 | | 1 | | | 050-099, 162-199 |
| 108 | 20 | | PA | 3-9 | 21-66-11 | D13874 | | 7 | | GD01916 | S.. | 2 | | | 050-099, 162-199 |
| 109 | 22 | | PA | 19-5 | 21-66-11 | D13876 | | 24 | | D13872 | | 6 | | | 050-099 |
| 109 | 22 | | PA | 19-1 | 21-66-11 | D13876 | | 24 | | D13872 | | 6 | | | 162-199 |
| 110 | 22 | | PA | 19-5 | 21-66-11 | D13876 | | 25 | | D13872 | | 5 | | | 050-099 |
| 110 | 22 | | PA | 19-1 | 21-66-11 | D13876 | | 25 | | D13872 | | 5 | | | 162-199 |
| 111 | 20 | | PA | 3-7 | 21-66-11 | D13876 | | 23 | | GD01916 | S.. | 2 | | | 050-099 |
| 111 | 20 | | PA | 3-5 | 21-66-11 | D13876 | | 23 | | GD01916 | S.. | 2 | | | 162-199 |
| 112 | 20 | | PA | 9-4 | 21-66-11 | D13860 | | 4 | | GD04170 | S.. | 2 | | | 050-099 |
| 112 | 20 | | PA | 9-6 | 21-66-11 | D13860 | | 4 | | GD04170 | S.. | 2 | | | 162-199 |
| 113 | 22 | | PA | 17-6 | 21-66-11 | D06934P | | 11 | | SM00001 | | S | | | 050-099 |
| 113 | 22 | | PA | 2-11 | 21-66-11 | D06934P | | 11 | | SM00001 | | S | | | 162-199 |
| 114 | 22 | | PA | 44-1 | 21-66-11 | D06934P | | 9 | | D06936J | | 3 | | | 050-099 |
| 114 | 22 | | PA | 44-0 | 21-66-11 | D06934P | | 9 | | D06936J | | 3 | | | 162-199 |
| 115 | 22 | | PA | 44-1 | 21-66-11 | D06934P | | 10 | | D06936J | | 4 | | | 050-099 |
| 115 | 22 | | PA | 44-0 | 21-66-11 | D06934P | | 10 | | D06936J | | 4 | | | 162-199 |
| 116 | 22 | | PA | 44-1 | 21-66-11 | D06934P | | 12 | | D06936J | | 5 | | | 050-099 |
| 116 | 22 | | PA | 44-0 | 21-66-11 | D06934P | | 12 | | D06936J | | 5 | | | 162-199 |
| 117 | 20 | | PA | 12-4 | 21-66-11 | D13856 | | 7 | | GD04170 | D.. | 2 | | | 050-099, 162-199 |
| 118 | 22 | | PA | 52-0 | 21-66-11 | D13856 | | 6 | | D06936J | | 9 | | | 050-099, 162-199 |
| 119 | 22 | | PA | 42-7 | 21-66-11 | D13856 | | 2 | | D06934P | | 13 | | | 050-099 |
| 119 | 22 | | PA | 42-6 | 21-66-11 | D06934P | | 13 | | D13856 | | 2 | | | 162-199 |
| 120 | 20 | | PA | 12-4 | 21-66-11 | D13856 | | 3 | | GD04170 | A.. | 2 | | | 050-099, 162-199 |
| 121 | 22 | | PA | 42-7 | 21-66-11 | D13856 | | 1 | | D06934P | | 14 | | | 050-099 |
| 121 | 22 | | PA | 42-6 | 21-66-11 | D06934P | | 14 | | D13856 | | 1 | | | 162-199 |
| 122 | 20 | | PA | 12-4 | 21-66-11 | D13856 | | 5 | | GD04170 | D.. | 2 | | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1232 | 286T1232 | | | P36 TO P19 AC FEEDER (continued) | | | | | | | | | | | | | |
| 124 | 22 | | PA | 26-2 | 21-66-11 | D13856 | | 4 | | | | | SM00001 | | S | | 050-099 |
| 124 | 22 | | PA | 40-2 | 21-66-11 | D13856 | | 4 | | | | | SM00001 | | S | | 162-199 |
| 125 | 22 | | PA | 27-8 | 21-66-11 | D06936J | | 8 | | | | | SM00001 | | S | | 050-099 |
| 125 | 22 | | PA | 41-7 | 21-66-11 | SM00001 | | | | S | | | D06936J | 8 | | | 162-199 |
| 126 | 22 | | PA | 44-1 | 21-66-11 | D06934P | | 17 | | | | | D06936J | 10 | | | 050-099 |
| 126 | 22 | | PA | 44-0 | 21-66-11 | D06934P | | 17 | | | | | D06936J | 10 | | | 162-199 |
| 127 | 22 | | PA | 44-1 | 21-66-11 | D06934P | | 18 | | | | | D06936J | 11 | | | 050-099 |
| 127 | 22 | | PA | 44-0 | 21-66-11 | D06934P | | 18 | | | | | D06936J | 11 | | | 162-199 |
| 128 | 20 | | PA | 5-3 | 21-66-11 | D13872 | | 3 | | | | | GD01920 | A.. | 2 | | 050-099 |
| 128 | 20 | | PA | 5-2 | 21-66-11 | D13872 | | 3 | | | | | GD01920 | A.. | 2 | | 162-199 |
| 131 | 22 | | PA | 44-1 | 21-66-11 | D06934P | | 15 | | | | | D06936J | 6 | | | 050-099 |
| 131 | 22 | | PA | 44-0 | 21-66-11 | D06934P | | 15 | | | | | D06936J | 6 | | | 162-199 |
| 132 | 22 | | PA | 44-1 | 21-66-11 | D06934P | | 16 | | | | | D06936J | 7 | | | 050-099 |
| 132 | 22 | | PA | 44-0 | 21-66-11 | D06934P | | 16 | | | | | D06936J | 7 | | | 162-199 |
| 137 | 20 | | PA | 4-7 | 21-66-31 | D13922 | | 8 | | | | | GD01776 | A.. | 2 | | 050-099 |
| 137 | 20 | | PA | 5-0 | 21-66-31 | D13922 | | 8 | | | | | GD01776 | A.. | 2 | | 150, 152-157 |
| 137 | 20 | | PA | 4-8 | 21-66-31 | D13922 | | 8 | | | | | GD01776 | A.. | 2 | | 162-199 |
| 138 | 20 | | PA | 4-7 | 21-66-31 | D13922 | | 7 | | | | | GD01776 | S.. | 2 | | 050-099 |
| 138 | 20 | | PA | 5-0 | 21-66-31 | D13922 | | 7 | | | | | GD01776 | S.. | 2 | | 150, 152-157 |
| 138 | 20 | | PA | 4-8 | 21-66-31 | D13922 | | 7 | | | | | GD01776 | S.. | 2 | | 162-199 |
| 139 | 22 | | PA | 123-4 | 21-66-31 | D13926 | | 31 | | | | | D06934P | 23 | | | 050-099 |
| 139 | 22 | | PA | 144-3 | 21-66-31 | D13926 | | 31 | | | | | D06934P | 23 | | | 150, 152-157 |
| 139 | 22 | | PA | 144-6 | 21-66-31 | D13926 | | 31 | | | | | D06934P | 23 | | | 162-199 |
| 140 | 22 | | PA | 123-4 | 21-66-31 | D13926 | | 18 | | | | | D06934P | 19 | | | 050-099 |
| 140 | 22 | | PA | 144-3 | 21-66-31 | D13926 | | 18 | | | | | D06934P | 19 | | | 150, 152-157 |
| 140 | 22 | | PA | 144-6 | 21-66-31 | D13926 | | 18 | | | | | D06934P | 19 | | | 162-199 |
| 141 | 20 | | PA | 4-5 | 21-66-31 | D13926 | | 13 | | | | | GD01776 | D.. | 2 | | 050-099 |
| 141 | 20 | | PA | 4-6 | 21-66-31 | D13926 | | 13 | | | | | GD01776 | D.. | 2 | | 150, 152-199 |
| 142 | 22 | | PA | 0-7 | 21-66-31 | D13926 | | 15 | | | | | D13926 | 16 | | | 050-099 |
| 142 | 22 | | PA | 6-0 | 21-66-31 | D13926 | | 15 | | | | | D13926 | 16 | | | 150, 152-199 |
| 143 | 20 | | PA | 4-5 | 21-66-31 | D13926 | | 60 | | | | | GD01776 | S.. | 2 | | 050-099 |
| 143 | 20 | | PA | 4-6 | 21-66-31 | D13926 | | 60 | | | | | GD01776 | S.. | 2 | | 150, 152-199 |
| 144 | 20 | | PA | 4-7 | 21-66-31 | D13924 | | 23 | | | | | GD01776 | S.. | 2 | | 050-099, 150, 152-199 |
| 145 | 20 | | PA | 2-3 | 21-66-31 | D13894 | | 3 | | | | | GD01776 | S.. | 2 | | 050-099 |
| 145 | 20 | | PA | 2-2 | 21-66-31 | D13894 | | 3 | | | | | GD01776 | S.. | 2 | | 150, 152-199 |
| 146 | 20 | | PA | 3-6 | 21-66-31 | D13896 | | 4 | | | | | GD01776 | S.. | 2 | | 050-099 |
| 146 | 20 | | PA | 3-5 | 21-66-31 | D13896 | | 4 | | | | | GD01776 | S.. | 2 | | 150, 152-199 |
| 147 | 20 | | PA | 121-10 | 21-66-31 | D13896 | | 1 | | | | | D06934P | 26 | | | 050-099 |
| 147 | 20 | | PA | 142-9 | 21-66-31 | D06934P | | 26 | | | | | D13896 | 1 | | | 150, 152-157 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1232 | 286T1232 | | | P36 TO P19 AC FEEDER (continued) | | | | | | | | | | | |
| 147 | 20 | | PA | 142-11 | 21-66-31 | D06934P | | 26 | | | D13896 | | 1 | | 162-199 |
| 148 | 20 | | PA | 121-10 | 21-66-31 | D13896 | | 2 | | | D06934P | | 27 | | 050-099 |
| 148 | 20 | | PA | 142-9 | 21-66-31 | D06934P | | 27 | | | D13896 | | 2 | | 150, 152-157 |
| 148 | 20 | | PA | 142-11 | 21-66-31 | D06934P | | 27 | | | D13896 | | 2 | | 162-199 |
| 149 | 20 | | PA | 121-10 | 21-66-31 | D13896 | | 3 | | | D06934P | | 29 | | 050-099 |
| 149 | 20 | | PA | 142-9 | 21-66-31 | D06934P | | 29 | | | D13896 | | 3 | | 150, 152-157 |
| 149 | 20 | | PA | 142-11 | 21-66-31 | D06934P | | 29 | | | D13896 | | 3 | | 162-199 |
| 150 | 22 | | PA | 123-4 | 21-66-31 | D13926 | | 29 | | | D06934P | | 25 | | 050-099 |
| 150 | 22 | | PA | 144-3 | 21-66-31 | D06934P | | 25 | | | D13926 | | 29 | | 150, 152-157 |
| 150 | 22 | | PA | 144-6 | 21-66-31 | D06934P | | 25 | | | D13926 | | 29 | | 162-199 |
| 151 | 22 | | PA | 2-0 | 21-66-31 | D13926 | | 43 | | | D13926 | | 48 | | 050-099, 150, 152-199 |
| 152 | 22 | | PA | 123-4 | 21-66-31 | D13926 | | 32 | | | D06934P | | 28 | | 050-099 |
| 152 | 22 | | PA | 144-3 | 21-66-31 | D06934P | | 28 | | | D13926 | | 32 | | 150, 152-157 |
| 152 | 22 | | PA | 144-6 | 21-66-31 | D06934P | | 28 | | | D13926 | | 32 | | 162-199 |
| 153 | 22 | | PA | 99-5 | 21-66-31 | D13926 | | 33 | | | D04282P | | 10 | | 050-099 |
| 153 | 22 | | PA | 122-0 | 21-66-31 | D04282P | | 2 | | | D13926 | | 33 | | 150, 152-157 |
| 153 | 22 | | PA | 120-8 | 21-66-31 | D04282P | | 2 | | | D13926 | | 33 | | 162-199 |
| 157 | 22 | | PA | 36-4 | 21-66-31 | D06934P | | 33 | | | D04282P | | 14 | | 050-099 |
| 157 | 22 | | PA | 37-0 | 21-66-31 | D06934P | | 33 | | | D04282P | | 14 | | 150, 152-157 |
| 157 | 22 | | PA | 36-3 | 21-66-31 | D06934P | | 33 | | | D04282P | | 14 | | 162-199 |
| 158 | 22 | | PA | 36-4 | 21-66-31 | D06934P | | 24 | | | D04282P | | 13 | | 050-099 |
| 158 | 22 | | PA | 37-0 | 21-66-31 | D06934P | | 24 | | | D04282P | | 13 | | 150, 152-157 |
| 158 | 22 | | PA | 36-3 | 21-66-31 | D06934P | | 24 | | | D04282P | | 13 | | 162-199 |
| 175 | 24 | | PK | 16-0 | 21-45-24 | D06934P | | 37 | | | D07126P | | 2 | | 050-099, 150-157, 275-277 |
| 175 | 24 | | PK | 12-3 | 21-45-24 | D06934P | | 37 | | | D07126P | | 2 | | 278 |
| 175 | 24 | | PK | 12-1 | 21-45-24 | D06934P | | 37 | | | D07126P | | 2 | | 280-299 |
| 176 | 24 | | PK | 16-0 | 21-45-24 | D06934P | | 38 | | | D07126P | | 1 | | 050-099, 150-157, 275-277 |
| 176 | 24 | | PK | 12-3 | 21-45-24 | D06934P | | 38 | | | D07126P | | 1 | | 278 |
| 176 | 24 | | PK | 12-1 | 21-45-24 | D06934P | | 38 | | | D07126P | | 1 | | 280-299 |
| 200B | 22 | | PB HY | 3-10 | 21-66-31 | D13926 | | 3 | | | D13890 | | 1 | | 050-099 |
| 200B | 22 | | PB HY | 1-5 | 21-66-31 | D13926 | | 3 | | | D13890 | | 1 | | 150, 152-157 |
| 200B | 22 | | PB HY | 3-11 | 21-66-31 | D13926 | | 3 | | | D13890 | | 1 | | 162-199 |
| 200R | 22 | | PB HY | 0-0 | 21-66-31 | D13926 | | 4 | | | D13890 | | 3 | | 050-099, 150, 152-199 |
| 201B | 22 | | PB IA | 12-0 | 21-66-31 | D13926 | | 5 | | | D13892 | | 1 | | 050-099, 150, 152-199 |
| 201R | 22 | | PB IA | 0-0 | 21-66-31 | D13926 | | 6 | | | D13892 | | 2 | | 050-099, 150, 152-199 |
| 202 | 20 | | PA | 3-9 | 21-66-11 | D13874 | | | | FA | GD01916 | | S.. | 2 | 050-099, 162-199 |
| 202B | 18 | | PR IB | 6-7 | 21-66-11 | D13874 | | 5 | DK | | D13870 | | 4 | DK | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|--------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1232 | 286T1232 | | | P36 TO P19 AC FEEDER (continued) | | | | | | | | | | | |
| 202B | 18 | | PR | IB | 6-8 | 21-66-11 | D13874 | 5 | DK | | D13870 | 4 | DK | | 162-199 |
| 202R | 18 | | PR | IB | 0-0 | 21-66-11 | D13874 | 12 | DK | | D13870 | 2 | DK | | 050-099, 162-199 |
| 202Z | | | | IB | 0-0 | 21-66-11 | D13874 | | | FA | D13870 | DED | | | 050-099, 162-199 |
| 203 | 20 | | PA | | 3-7 | 21-66-11 | D13876 | | | FB | GD01916 | S.. | 2 | | 050-099 |
| 203 | 20 | | PA | | 3-5 | 21-66-11 | D13876 | | | FB | GD01916 | S.. | 2 | | 162-199 |
| 203B | 22 | | PR | IC | 37-5 | 21-66-11 | D13876 | 22 | | | D06934P | 34 | | | 050-099 |
| 203B | 22 | | PR | IC | 37-1 | 21-66-11 | D06934P | 34 | | | D13876 | 22 | | | 162-199 |
| 203R | 22 | | PR | IC | 0-0 | 21-66-11 | D13876 | 21 | | | D06934P | 35 | | | 050-099 |
| 203R | 22 | | PR | IC | 0-0 | 21-66-11 | D06934P | 35 | | | D13876 | 21 | | | 162-199 |
| 203Z | | | | IC | 0-0 | 21-66-11 | D13876 | | | FB | D06934P | 36 | | | 050-099 |
| 203Z | | | | IC | 0-0 | 21-66-11 | D06934P | 36 | | | D13876 | | | FB | 162-199 |
| 204 | 20 | | UA | | 4-7 | 21-66-31 | D13924 | | | FD | GD01776 | S.. | 2 | | 050-099, 150, 152-199 |
| 204B | 22 | | PR | ID | 123-6 | 21-66-31 | D13924 | 22 | | | D06934P | 31 | | | 050-099 |
| 204B | 22 | | PR | ID | 144-4 | 21-66-31 | D06934P | 31 | | | D13924 | 22 | | | 150, 152-157 |
| 204B | 22 | | PR | ID | 144-7 | 21-66-31 | D06934P | 31 | | | D13924 | 22 | | | 162-199 |
| 204R | 22 | | PR | ID | 0-0 | 21-66-31 | D13924 | 21 | | | D06934P | 30 | | | 050-099 |
| 204R | 22 | | PR | ID | 0-0 | 21-66-31 | D06934P | 30 | | | D13924 | 21 | | | 150, 152-199 |
| 204Z | | | | ID | 0-0 | 21-66-31 | D13924 | | | FD | D06934P | 32 | | | 050-099 |
| 204Z | | | | ID | 0-0 | 21-66-31 | D06934P | 32 | | | D13924 | | | FD | 150, 152-199 |
| 205B | 18 | | PR | IE | 165-0 | 21-45-24 | D07126P | 23 | DK | | SM00011 | | 9 | | 050-099 |
| 205B | 18 | | VG | IE | 165-0 | 21-45-24 | D07126P | 23 | | | SM00011 | | 9 | | 150-199, 275-277 |
| 205B | 18 | | PR | IE | 151-6 | 21-45-24 | D07126P | 23 | | | SM00011 | | 9 | | 278 |
| 205B | 18 | | PR | IE | 151-9 | 21-45-24 | D07126P | 23 | | | SM00011 | | 9 | | 280-299 |
| 205R | 18 | | PR | IE | 0-0 | 21-45-24 | D07126P | 21 | DK | | SM00010 | | 9 | | 050-099 |
| 205R | 18 | | VG | IE | 0-0 | 21-45-24 | D07126P | 21 | | | SM00010 | | 9 | | 150-199, 275-277 |
| 205R | 18 | | PR | IE | 0-0 | 21-45-24 | D07126P | 21 | | | SM00010 | | 9 | | 278-299 |
| 205Z | | | | IE | 0-0 | 21-45-24 | D07126P | 22 | | | SM00012 | | 9 | | ALL |
| 300B | 18 | | PC | LY | 37-7 | 21-66-11 | D13874 | 11 | DK | | D06934P | 4 | DL | | 050-099 |
| 300B | 18 | | PC | LY | 37-6 | 21-66-11 | D06934P | 4 | DL | | D13874 | 11 | DK | | 162-199 |
| 300R | 18 | | PC | LY | 0-0 | 21-66-11 | D13874 | 9 | DK | | D06934P | 2 | DL | | 050-099 |
| 300R | 18 | | PC | LY | 0-0 | 21-66-11 | D06934P | 2 | DL | | D13874 | 9 | DK | | 162-199 |
| 300Y | 18 | | PC | LY | 0-0 | 21-66-11 | D13874 | 10 | DK | | D06934P | 3 | DL | | 050-099 |
| 300Y | 18 | | PC | LY | 0-0 | 21-66-11 | D06934P | 3 | DL | | D13874 | 10 | DK | | 162-199 |
| 301B | 22 | | PC | MA | 39-6 | 21-66-11 | D13860 | 3 | | | D06934P | 8 | | | 050-099 |
| 301B | 22 | | PC | MA | 39-8 | 21-66-11 | D13860 | 3 | | | D06934P | 8 | | | 162-199 |
| 301R | 22 | | PC | MA | 0-0 | 21-66-11 | D13860 | 1 | | | D06934P | 6 | | | 050-099, 162-199 |
| 301Y | 22 | | PC | MA | 0-0 | 21-66-11 | D13860 | 2 | | | D06934P | 7 | | | 050-099, 162-199 |
| 302B | 18 | | PC | MB | 123-6 | 21-66-31 | D13922 | 11 | DK | | D06934P | 22 | DL | | 050-099 |
| 302B | 18 | | PC | MB | 144-10 | 21-66-31 | D13922 | 11 | DK | | D06934P | 22 | DL | | 150, 152-157 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1232 | 286T1232 | | | P36 TO P19 AC FEEDER (continued) | | | | | | | | | | | |
| 302B | 18 | PC | MB | | 144-8 | 21-66-31 | D13922 | 11 | DK | | D06934P | 22 | DL | | 162-199 |
| 302R | 18 | PC | MB | | 0-0 | 21-66-31 | D13922 | 9 | DK | | D06934P | 20 | DL | | 050-099, 150, 152-199 |
| 302Y | 18 | PC | MB | | 0-0 | 21-66-31 | D13922 | 10 | DK | | D06934P | 21 | DL | | 050-099, 150, 152-199 |
| 303B | 22 | PC | MC | | 15-6 | 21-66-31 | D13926 | 8 | | | D13898 | A | | | 050-099 |
| 303B | 22 | PC | MC | | 15-2 | 21-66-31 | D13926 | 8 | | | D13898 | A | | | 150, 152-199 |
| 303R | 22 | PC | MC | | 0-0 | 21-66-31 | D13926 | 9 | | | D13898 | B | | | 050-099, 150, 152-199 |
| 303Y | 22 | PC | MC | | 0-0 | 21-66-31 | D13926 | 10 | | | D13898 | C | | | 050-099, 150, 152-199 |
| 304 | 18 | UA | | | 4-7 | 21-66-31 | D13922 | | | FC | GD01776 | S.. | 2 | | 050-099 |
| 304 | 18 | UA | | | 5-0 | 21-66-31 | D13922 | | | FC | GD01776 | S.. | 2 | | 150, 152-157 |
| 304 | 18 | UA | | | 4-8 | 21-66-31 | D13922 | | | FC | GD01776 | S.. | 2 | | 162-199 |
| 304B | 18 | PS | MD | | 5-2 | 21-66-31 | D13922 | 6 | DK | | D13894 | 1 | DK | | 050-099 |
| 304B | 18 | PS | MD | | 6-1 | 21-66-31 | D13922 | 6 | DK | | D13894 | 1 | DK | | 150, 152-157 |
| 304B | 18 | PS | MD | | 5-3 | 21-66-31 | D13922 | 6 | DK | | D13894 | 1 | DK | | 162-199 |
| 304R | 18 | PS | MD | | 0-0 | 21-66-31 | D13922 | 5 | DK | | D13894 | 4 | DK | | 050-099, 150, 152-199 |
| 304Y | 18 | PS | MD | | 0-0 | 21-66-31 | D13922 | 4 | DK | | D13894 | 2 | DK | | 050-099, 150, 152-199 |
| 304Z | | | MD | | 0-0 | 21-66-31 | D13922 | | | FC | D13894 | DED | | | 050-099, 150, 152-199 |
| 305B | 18 | PS | ME | | 8-0 | 21-45-24 | D72026 | 2 | DK | | SM00011 | 9 | | | 050-099 |
| 305B | 18 | VH | ME | | 8-0 | 21-45-24 | D72026 | 2 | DK | | SM00011 | 9 | | | 150-199, 275-277 |
| 305B | 18 | PS | ME | | 6-0 | 21-45-24 | D72026 | 2 | DK | | SM00011 | 9 | | | 278 |
| 305B | 18 | PS | ME | | 4-11 | 21-45-24 | D72026 | 2 | DK | | SM00011 | 9 | | | 280-299 |
| 305R | 18 | PS | ME | | 0-0 | 21-45-24 | D72026 | 1 | DK | | SM00010 | 9 | | | 050-099, 278-299 |
| 305R | 18 | VH | ME | | 0-0 | 21-45-24 | D72026 | 1 | DK | | SM00010 | 9 | | | 150-199, 275-277 |
| 305Y | 18 | PS | ME | | 0-0 | 21-45-24 | D72026 | 4 | DK | | SM00010 | 9 | | | 050-099, 278-299 |
| 305Y | 18 | VH | ME | | 0-0 | 21-45-24 | D72026 | 4 | DK | | SM00010 | 9 | | | 150-199, 275-277 |
| 305Z | | | ME | | 0-0 | 21-45-24 | D72026 | | DED | | SM00012 | 9 | | | ALL |
| 306B | 18 | PS | MF | | 8-0 | 21-45-24 | D72028 | 2 | DK | | SM00011 | 9 | | | 050-099 |
| 306B | 18 | VH | MF | | 8-0 | 21-45-24 | D72028 | 2 | DK | | SM00011 | 9 | | | 150-199, 275-277 |
| 306B | 18 | PS | MF | | 6-6 | 21-45-24 | D72028 | 2 | DK | | SM00011 | 9 | | | 278 |
| 306B | 18 | PS | MF | | 5-5 | 21-45-24 | D72028 | 2 | DK | | SM00011 | 9 | | | 280-299 |
| 306R | 18 | PS | MF | | 0-0 | 21-45-24 | D72028 | 1 | DK | | SM00010 | 9 | | | 050-099, 278-299 |
| 306R | 18 | VH | MF | | 0-0 | 21-45-24 | D72028 | 1 | DK | | SM00010 | 9 | | | 150-199, 275-277 |
| 306Y | 18 | PS | MF | | 0-0 | 21-45-24 | D72028 | 4 | DK | | SM00010 | 9 | | | 050-099, 278-299 |
| 306Y | 18 | VH | MF | | 0-0 | 21-45-24 | D72028 | 4 | DK | | SM00010 | 9 | | | 150-199, 275-277 |
| 306Z | | | MF | | 0-0 | 21-45-24 | D72028 | | DED | | SM00012 | 9 | | | 050-099, 278-299 |
| 306Z | | | MF | | 0-0 | 21-45-24 | D72026 | | DED | | SM00012 | 9 | | | 150-199, 275-277 |
| 318B | 16 | PC | MR | | 10-0 | 21-73-11 | C09001 | B2 | D | | D09000 | L | | | 275-299 |
| 318R | 16 | PC | MR | | 0-0 | 21-73-11 | C09001 | A2 | D | | D09000 | K | | | 275-299 |
| 318Y | 16 | PC | MR | | 0-0 | 21-73-11 | C09001 | C2 | D | | D09000 | M | | | 275-299 |
| 319B | 16 | PC | MS | | 10-0 | 21-73-11 | C09002 | B2 | D | | D09001 | L | | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1230
Page 11
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1232 | 286T1232 | | | P36 TO P19 AC FEEDER (continued) | | | | | | | | | | | | |
| 319R | 16 | PC | MS | 0-0 | 21-73-11 | C09002 | A2 | D | | D09001 | | K | | 275-299 | | |
| 319Y | 16 | PC | MS | 0-0 | 21-73-11 | C09002 | C2 | D | | D09001 | | M | | 275-299 | | |
| 320B | 16 | PC | MT | 5-0 | 21-73-11 | C09003 | B2 | D | | D09002 | | L | | 275-278 | | |
| 320B | 16 | PC | MT | 10-0 | 21-73-11 | C09003 | B2 | D | | D09002 | | L | | 280-299 | | |
| 320R | 16 | PC | MT | 0-0 | 21-73-11 | C09003 | A2 | D | | D09002 | | K | | 275-299 | | |
| 320Y | 16 | PC | MT | 0-0 | 21-73-11 | C09003 | C2 | D | | D09002 | | M | | 275-299 | | |
| 504 | 18 | PA | | 10-0 | 21-45-24 | D72026 | 3 | DK | | GD00026 | S.. | 2 | | 050-099 | | |
| 504 | 18 | PJ | | 15-0 | 21-45-24 | D72026 | 3 | DK | | GD00026 | S.. | 2 | | 150-199, 275-277 | | |
| 504 | 18 | PA | | 4-9 | 21-45-24 | D72026 | 3 | DK | | GD00026 | S.. | 2 | | 278-299 | | |
| 509 | 18 | PA | | 15-0 | 21-45-24 | D72028 | 3 | DK | | GD00020 | S.. | 2 | | 050-099 | | |
| 509 | 18 | PJ | | 15-0 | 21-45-24 | D72028 | 3 | DK | | GD00020 | S.. | 2 | | 150-199, 275-277 | | |
| 509 | 18 | PA | | 5-3 | 21-45-24 | D72028 | 3 | DK | | GD00020 | S.. | 2 | | 278-299 | | |
| 510 | 20 | PA | | 170-0 | 21-45-24 | D72030 | 1 | | | D07126P | | 12 | | 050-099 | | |
| 510 | 20 | PJ | | 170-0 | 21-45-24 | D72030 | 1 | | | D07126P | | 12 | | 150-199, 275-277 | | |
| 510 | 20 | PA | | 156-6 | 21-45-24 | D72030 | 1 | | | D07126P | | 12 | | 278 | | |
| 510 | 20 | PA | | 156-2 | 21-45-24 | D72030 | 1 | | | D07126P | | 12 | | 280-299 | | |
| 511 | 20 | PA | | 170-0 | 21-45-24 | D72030 | 2 | | | D07126P | | 13 | | 050-099 | | |
| 511 | 20 | PJ | | 170-0 | 21-45-24 | D72030 | 2 | | | D07126P | | 13 | | 150-199, 275-277 | | |
| 511 | 20 | PA | | 156-6 | 21-45-24 | D72030 | 2 | | | D07126P | | 13 | | 278 | | |
| 511 | 20 | PA | | 156-2 | 21-45-24 | D72030 | 2 | | | D07126P | | 13 | | 280-299 | | |
| 512 | 20 | PA | | 170-0 | 21-45-24 | D72030 | 3 | | | D07126P | | 14 | | 050-099 | | |
| 512 | 20 | PJ | | 170-0 | 21-45-24 | D72030 | 3 | | | D07126P | | 14 | | 150-199, 275-277 | | |
| 512 | 20 | PA | | 156-6 | 21-45-24 | D72030 | 3 | | | D07126P | | 14 | | 278 | | |
| 512 | 20 | PA | | 156-2 | 21-45-24 | D72030 | 3 | | | D07126P | | 14 | | 280-299 | | |
| 513 | 20 | PA | | 7-0 | 21-45-24 | D72030 | 4 | | | GD00026 | S.. | 2 | | 050-099 | | |
| 513 | 20 | PJ | | 7-0 | 21-45-24 | D72030 | 4 | | | GD00026 | S.. | 2 | | 150-199, 275-277 | | |
| 513 | 20 | PA | | 4-10 | 21-45-24 | D72030 | 4 | | | GD00026 | S.. | 2 | | 278-299 | | |
| 514 | 20 | PA | | 175-0 | 21-45-24 | D72032 | 1 | | | D07126P | | 15 | | 050-099 | | |
| 514 | 20 | PJ | | 175-0 | 21-45-24 | D72032 | 1 | | | D07126P | | 15 | | 150-199, 275-277 | | |
| 514 | 20 | PA | | 156-10 | 21-45-24 | D72032 | 1 | | | D07126P | | 15 | | 278 | | |
| 514 | 20 | PA | | 156-5 | 21-45-24 | D72032 | 1 | | | D07126P | | 15 | | 280-299 | | |
| 515 | 20 | PA | | 175-0 | 21-45-24 | D72032 | 2 | | | D07126P | | 16 | | 050-099 | | |
| 515 | 20 | PJ | | 175-0 | 21-45-24 | D72032 | 2 | | | D07126P | | 16 | | 150-199, 275-277 | | |
| 515 | 20 | PA | | 156-10 | 21-45-24 | D72032 | 2 | | | D07126P | | 16 | | 278 | | |
| 515 | 20 | PA | | 156-5 | 21-45-24 | D72032 | 2 | | | D07126P | | 16 | | 280-299 | | |
| 516 | 20 | PA | | 175-0 | 21-45-24 | D72032 | 3 | | | D07126P | | 17 | | 050-099 | | |
| 516 | 20 | PJ | | 175-0 | 21-45-24 | D72032 | 3 | | | D07126P | | 17 | | 150-199, 275-277 | | |
| 516 | 20 | PA | | 156-10 | 21-45-24 | D72032 | 3 | | | D07126P | | 17 | | 278 | | |
| 516 | 20 | PA | | 156-5 | 21-45-24 | D72032 | 3 | | | D07126P | | 17 | | 280-299 | | |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|----|-----------------|----|-----|-------------|--|---------|------|------|--------|---------|---------|------|--------|------------------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1232 | | 286T1232 | | | | P36 TO P19 AC FEEDER (continued) | | | | | | | | | | |
| 517 | 20 | PA | | | 15-0 | 21-45-24 | D72032 | | | 4 | GD00020 | S.. | 2 | | 050-099 | |
| 517 | 20 | PJ | | | 15-0 | 21-45-24 | D72032 | | | 4 | GD00020 | S.. | 2 | | 150-199, 275-277 | |
| 517 | 20 | PA | | | 5-1 | 21-45-24 | D72032 | | | 4 | GD00020 | S.. | 2 | | 278-299 | |
| 520 | 20 | PJ | | | 80-0 | SPARE | D06934P | | | 3 | D07126P | | 36 | | 150-157 | |
| 520 | 20 | PJ | | | 80-0 | SPARE | D06934P | | CAP | Y | D07126P | | 36 | | 275-277 | |
| 520 | 20 | PA | | | 12-3 | SPARE | D06934P | | CAP | Y | D07126P | | 36 | | 278 | |
| 520 | 20 | PA | | | 12-1 | SPARE | D06934P | | CAP | Y | D07126P | | 36 | | 280-299 | |
| 521 | 20 | PJ | | | 15-0 | SPARE | D06934P | | | 4 | D07126P | | 37 | | 150-157, 275-277 | |
| 521 | 20 | PA | | | 12-3 | SPARE | D06934P | | | 4 | D07126P | | 37 | | 278 | |
| 521 | 20 | PA | | | 12-1 | SPARE | D06934P | | | 4 | D07126P | | 37 | | 280-299 | |
| 522 | 20 | PJ | | | 15-0 | SPARE | D06934P | | | 5 | D07126P | | 38 | | 150-157, 275-277 | |
| 522 | 20 | PA | | | 12-3 | SPARE | D06934P | | | 5 | D07126P | | 38 | | 278 | |
| 522 | 20 | PA | | | 12-1 | SPARE | D06934P | | | 5 | D07126P | | 38 | | 280-299 | |
| 523 | 20 | PJ | | | 15-0 | SPARE | D06934P | | | 6 | D07126P | | 39 | | 150-157, 275-277 | |
| 523 | 20 | PA | | | 12-3 | SPARE | D06934P | | | 6 | D07126P | | 39 | | 278 | |
| 523 | 20 | PA | | | 12-1 | SPARE | D06934P | | | 6 | D07126P | | 39 | | 280-299 | |
| 557 | 12 | PA | | | 42-9 | 21-73-11 | SP07128 | | | 9 | C09001 | A1 | D | | 275-299 | |
| 558 | 12 | PA | | | 42-9 | 21-73-11 | SP07130 | | | 9 | C09001 | B1 | D | | 275-299 | |
| 559 | 12 | PA | | | 42-9 | 21-73-11 | SP07132 | | | 9 | C09001 | C1 | D | | 275-299 | |
| 560 | 20 | PA | | | 46-6 | 21-73-11 | D06934P | | | 3 | C09004 | | D | | 275-299 | |
| 561 | 16 | PA | | | 23-3 | 21-73-11 | GD01022 | | A.. | E | D09000 | | J | | 275-278 | |
| 561 | 16 | PA | | | 23-0 | 21-73-11 | GD01022 | | A.. | E | D09000 | | J | | 280-299 | |
| 562 | 20 | PA | | | 23-3 | 21-73-11 | GD02534 | | D.. | E | D09000 | | D | | 275-299 | |
| 564 | 16 | PA | | | 17-6 | 21-73-11 | GD04660 | | A.. | E | D09001 | | J | | 275-299 | |
| 565 | 20 | PA | | | 17-6 | 21-73-11 | GD04654 | | D.. | E | D09001 | | D | | 275-299 | |
| 567 | 16 | PA | | | 19-3 | 21-73-11 | GD01580 | | A.. | E | D09002 | | J | | 275-299 | |
| 568 | 20 | PA | | | 19-3 | 21-73-11 | GD02560 | | D.. | E | D09002 | | D | | 275-299 | |
| 570 | 20 | PA | | | 15-2 | 21-73-11 | C09004 | | | 2 | D | D09000 | | C | 275-299 | |
| 571 | 20 | PA | | | 93-5 | 21-73-11 | C09005 | | | 2 | D | D09001 | | C | 275-299 | |
| 572 | 20 | PA | | | 133-2 | 21-73-11 | C09006 | | | 2 | D | D09002 | | C | 275-299 | |
| W1234 | | 286T1234 | | | | LEFT MID ATT WORK & NIGHT LTS | | | | | | | | | | |
| 001 | 16 | PA | | | 58-0 | 33-26-21 | D05138P | | | 1 | FL | D05144P | | 1 | FM | 050-099 |
| 001 | 20 | PA | | | 68-3 | 33-26-21 | D05138P | | | 1 | | D05144P | | 1 | | 150-199, 275-278 |
| 001 | 20 | PA | | | 69-0 | 33-26-21 | D05138P | | | 1 | | D05144P | | 1 | | 280-299 |
| 004 | 20 | PA | | | 66-5 | 33-21-21 | D05138P | | | 4 | | L00462 | | =P | C | * 275-278 |
| 004 | 20 | PA | | | 66-0 | 33-21-21 | D05138P | | | 4 | | L00462 | | =P | C | * 280-299 |
| 005 | 22 | PA | | | 11-10 | 33-21-21 | D05138P | | | 5 | | L00455 | | =P | C | 275-278 |
| 005 | 22 | PA | | | 12-0 | 33-21-21 | D05138P | | | 5 | | L00455 | | =P | C | 280-299 |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1234 | 286T1234 | | | LEFT MID ATT WORK & NIGHT LTS (continued) | | | | | | | | | | | |
| 009 | 22 | | PA | | 44-0 | 33-21-21 | L00460 | =P | C | | D05138P | 3 | | | 050-099 |
| 009 | 22 | | PA | | 52-11 | 33-21-21 | D05138P | 2 | | | L00460 | =P | C | | 275-278 |
| 009 | 22 | | PA | | 53-0 | 33-21-21 | D05138P | 2 | | | L00460 | =P | C | | 280-299 |
| 013 | 20 | | PA | | 6-0 | 33-21-21 | L00460 | =G | C | | GD01014 | A.. | E | | 050-099 |
| 013 | 20 | | PA | | 6-8 | 33-21-21 | L00460 | =G | C | | GD01014 | A.. | E | | 275-278 |
| 013 | 20 | | PA | | 7-0 | 33-21-21 | L00460 | =G | C | | GD01014 | A.. | E | | 280-299 |
| 015 | 20 | | PA | | 12-7 | 33-21-21 | L00462 | =G | C | | GD04910 | A.. | E | | 150-199 |
| 015 | 20 | | PA | | 4-7 | 33-21-21 | L00462 | =G | C | | GD04866 | A.. | E | | 275-278 |
| 015 | 20 | | PA | | 6-0 | 33-21-21 | L00462 | =G | C | | GD04866 | A.. | E | | 280-299 |
| 017 | 20 | | PA | | 4-11 | 33-21-21 | L00455 | =G | C | | GD01022 | A.. | E | | 275-278 |
| 017 | 20 | | PA | | 5-0 | 33-21-21 | L00455 | =G | C | | GD01022 | A.. | E | | 280-299 |
| 019 | 22 | | PA | | 10-5 | 33-21-21 | L00462 | =P | C | | D05144P | 2 | | | 150-199 |
| 019 | 20 | | PA | | 14-2 | 33-21-21 | L00462 | =P | C | * | D05144P | 2 | | | 275-278 |
| 019 | 20 | | PA | | 15-0 | 33-21-21 | L00462 | =P | C | * | D05144P | 2 | | | 280-299 |
| 020 | 24 | | PK | | 57-0 | 33-21-31 | D05138P | 8 | | | D05144P | 5 | | | 050-099 |
| 020 | 24 | | PK | | 68-3 | 33-21-31 | D05138P | 8 | | | D05144P | 5 | | | 150-199, 275-278 |
| 020 | 24 | | PK | | 69-0 | 33-21-31 | D05138P | 8 | | | D05144P | 5 | | | 280-299 |
| 021 | 22 | | PA | | 16-0 | 21-61-21 | D05138P | 9 | | | SM00005 | | S | | 050-099 |
| 021 | 22 | | PA | | 15-10 | 21-61-21 | D05138P | 9 | | | SM00005 | | S | | 150-199, 275-278 |
| 021 | 22 | | PA | | 14-0 | 21-61-21 | D05138P | 9 | | | SM00005 | | S | | 280-299 |
| 022 | 20 | | PA | | 7-0 | 21-61-21 | D03824 | 2 | | | GD00960 | D.. | 2 | | 050-099 |
| 022 | 20 | | PA | | 3-6 | 21-61-21 | D03824 | 2 | | | GD05080 | D.. | 2 | | 150-199, 275-278 |
| 022 | 20 | | PA | | 5-0 | 21-61-21 | D03824 | 2 | | | GD05080 | D.. | 2 | | 280-299 |
| 023 | 20 | | PA | | 1-0 | 21-65-11 | D02604 | | B | | SM00001 | | S | | ALL |
| 024 | 20 | | PA | | 6-0 | 21-65-11 | SM00001 | | | S | GD00960 | D.. | 2 | | 050-099 |
| 024 | 20 | | PA | | 2-4 | 21-65-11 | SM00001 | | | S | GD05080 | D.. | 2 | | 150-199, 275-278 |
| 024 | 20 | | PA | | 4-0 | 21-65-11 | SM00001 | | | S | GD05080 | D.. | 2 | | 280-299 |
| 027 | 22 | | PA | | 65-0 | 21-61-41 | D05138P | 16 | | | SM00006 | | S | | 050-099 |
| 027 | 22 | | PA | | 48-9 | 21-61-41 | D05138P | 16 | | | SM00006 | | S | | 150-199, 275-278 |
| 027 | 22 | | PA | | 50-0 | 21-61-41 | D05138P | 16 | | | SM00006 | | S | | 280-299 |
| 028 | 20 | | PA | | 1-0 | 21-65-11 | SM00003 | | | S | D10714 | | B | | ALL |
| 029 | 20 | | PA | | 6-0 | 21-65-11 | SM00003 | | | S | GD01940 | D.. | 2 | | 050-099 |
| 029 | 20 | | PA | | 6-1 | 21-65-11 | SM00003 | | | S | GD01940 | D.. | 2 | | 150-199, 275-278 |
| 029 | 20 | | PA | | 7-0 | 21-65-11 | SM00003 | | | S | GD01940 | D.. | 2 | | 280-299 |
| 030 | 20 | | PA | | 1-0 | 21-65-11 | SM00002 | | | S | D10716 | | B | | ALL |
| 031 | 20 | | PA | | 6-0 | 21-65-11 | SM00002 | | | S | GD01906 | D.. | 2 | | 050-099 |
| 031 | 20 | | PA | | 11-2 | 21-65-11 | SM00002 | | | S | GD01906 | D.. | 2 | | 150-199, 275-278 |
| 031 | 20 | | PA | | 12-0 | 21-65-11 | SM00002 | | | S | GD01906 | D.. | 2 | | 280-299 |
| 032 | 20 | | PA | | 6-0 | 21-61-41 | GD01940 | | D.. | 2 | D10712 | | 2 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|----------|------|------|--------|----------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1234 | 286T1234 | | | LEFT MID ATT WORK & NIGHT LTS (continued) | | | | | | | | | | | |
| 032 | 20 | | PA | | 6-8 | 21-61-41 | GD01940 | D.. | 2 | | D10712 | 2 | | | 150-199, 275-278 |
| 032 | 20 | | PA | | 7-0 | 21-61-41 | GD01940 | D.. | 2 | | D10712 | 2 | | | 280-299 |
| 034 | 20 | | PA | | 5-4 | 33-21-21 | L00809 | =G | C | | GD04864 | A.. | E | | 150-199, 275-278 |
| 034 | 20 | | PA | | 6-0 | 33-21-21 | STA0675L | REF | * | | GD04864 | A.. | E | | 280-299 |
| 036 | 22 | | PA | | 40-0 | 33-21-21 | D05138P | | 3 | | L00809 | =P | C | * | 150-199 |
| 036 | 22 | | PA | | 40-0 | 33-21-21 | D05138P | | 3 | | L00809 | =P | C | | 275-278 |
| 036 | 22 | | PA | | 41-0 | 33-21-21 | D05138P | | 3 | | STA0675L | REF | * | | 280-299 |
| 040 | 22 | | PA | | 27-1 | 33-21-21 | L00809 | =P | C | * | L00460 | =P | C | | 150-199 |
| 041 | 20 | | PA | | 5-4 | 33-21-21 | GD00685 | A.. | E | | L00460 | =G | C | | 150-199 |
| 101 | 22 | | PA | | 59-0 | 33-21-21 | D05138P | | 2 | | D05144P | 9 | | | 050-099 |
| 101 | 22 | | PA | | 68-3 | 33-21-21 | D05144P | | 9 | | D05138P | 2 | | | 150-199 |
| 201B | 22 | | PB | A | 57-0 | 23-31-14 | D05138P | | 7 | | D05144P | 4 | | | 050-099 |
| 201B | 22 | | PB | A | 68-3 | 23-31-14 | D05138P | | 7 | | D05144P | 4 | | | 150-199, 275-278 |
| 201B | 22 | | PB | A | 69-0 | 23-31-14 | D05138P | | 7 | | D05144P | 4 | | | 280-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-14 | D05138P | | 6 | | D05144P | 3 | | | ALL |
| 202B | 20 | | PB | B | 32-0 | 21-65-11 | D05138P | | 10 | | D02604 | A | | | ALL |
| 202R | 20 | | PB | B | 0-0 | 21-65-11 | D05138P | | 11 | | SM00001 | | S | | ALL |
| 203B | 20 | | PB | C | 57-0 | 21-65-11 | D05138P | | 12 | | D05144P | 6 | | | 050-099 |
| 203B | 20 | | PB | C | 68-3 | 21-65-11 | D05138P | | 12 | | D05144P | 6 | | | 150-199, 275-278 |
| 203B | 20 | | PB | C | 69-0 | 21-65-11 | D05138P | | 12 | | D05144P | 6 | | | 280-299 |
| 203R | 20 | | PB | C | 0-0 | 21-65-11 | D05138P | | 13 | | D05144P | 7 | | | ALL |
| 204B | 24 | | PL | D | 43-0 | 21-61-41 | D05138P | | 18 | | D10708 | 1 | | | 050-099 |
| 204B | 24 | | PL | D | 53-1 | 21-61-41 | D05138P | | 18 | | D10708 | 1 | | | 150-199, 275-278 |
| 204B | 24 | | PL | D | 54-0 | 21-61-41 | D05138P | | 18 | | D10708 | 1 | | | 280-299 |
| 204R | 24 | | PL | D | 0-0 | 21-61-41 | D05138P | | 17 | | D10708 | 2 | | | ALL |
| 205B | 24 | | PL | E | 67-0 | 21-61-41 | D05138P | | 20 | | D10710 | 1 | | | 050-099 |
| 205B | 24 | | PL | E | 82-6 | 21-61-41 | D05138P | | 20 | | D10710 | 1 | | | 150-199, 275-278 |
| 205B | 24 | | PL | E | 81-0 | 21-61-41 | D05138P | | 20 | | D10710 | 1 | | | 280-299 |
| 205R | 24 | | PL | E | 0-0 | 21-61-41 | D05138P | | 19 | | D10710 | 2 | | | ALL |
| 206B | 20 | | PB | G | 67-0 | 21-65-11 | D05138P | | 23 | | D10716 | A | | | 050-099 |
| 206B | 20 | | PB | G | 82-6 | 21-65-11 | D05138P | | 23 | | D10716 | A | | | 150-199, 275-278 |
| 206B | 20 | | PB | G | 81-0 | 21-65-11 | D05138P | | 23 | | D10716 | A | | | 280-299 |
| 206R | 20 | | PB | G | 0-0 | 21-65-11 | D05138P | | 24 | | SM00002 | | S | | ALL |
| 207B | 20 | | PB | F | 43-0 | 21-65-11 | D05138P | | 21 | | D10714 | A | | | 050-099 |
| 207B | 20 | | PB | F | 53-0 | 21-65-11 | D05138P | | 21 | | D10714 | A | | | 150-199, 275-278 |
| 207B | 20 | | PB | F | 54-0 | 21-65-11 | D05138P | | 21 | | D10714 | A | | | 280-299 |
| 207R | 20 | | PB | F | 0-0 | 21-65-11 | D05138P | | 22 | | SM00003 | | S | | ALL |
| 800 | 22 | | PA | | 19-0 | 21-61-21 | D03824 | | 1 | | SM00005 | | S | | 050-099 |
| 800 | 22 | | PA | | 17-7 | 21-61-21 | SM00005 | | | S | D03824 | 1 | | | 150-199, 275-278 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 15

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1234 | 286T1234 | | | LEFT MID ATT WORK & NIGHT LTS (continued) | | | | | | | | | | | | | | |
| 800 | 22 | | PA | 18-0 | 21-61-21 | SM00005 | | | | | | | | D03824 | 1 | | | 280-299 |
| 801 | 24 | | PK | 7-0 | 21-61-61 | D13470 | | 1 | | | | | | SM00005 | | S | | 050-099 |
| 801 | 22 | | PA | 6-8 | 21-61-61 | SM00005 | | | | | | | | D13470 | 1 | | | 150-199 |
| 801 | 24 | | PK | 6-8 | 21-61-61 | SM00005 | | | | | | | | D13470 | 1 | | | 275-278 |
| 801 | 24 | | PK | 9-0 | 21-61-61 | SM00005 | | | | | | | | D13470 | 1 | | | 280-299 |
| 802 | 20 | | PA | 15-0 | 21-61-61 | D13470 | | | 2 | | | | | GD01924 | D.. | 2 | | 050-099 |
| 802 | 20 | | PA | 12-6 | 21-61-61 | GD01924 | | | D.. | 2 | | | | D13470 | 2 | | | 150-199, 275-278 |
| 802 | 20 | | PA | 14-0 | 21-61-61 | GD01924 | | | D.. | 2 | | | | D13470 | 2 | | | 280-299 |
| 803 | 22 | | PA | 6-0 | 21-61-41 | D10712 | | | 1 | | | | | SM00006 | | S | | 050-099, 280-299 |
| 803 | 22 | | PA | 4-3 | 21-61-41 | D10712 | | | 1 | | | | | SM00006 | | S | | 150-199, 275-278 |
| 804 | 20 | | PA | 5-0 | 21-61-71 | D13472 | | | 2 | | | | | GD01940 | D.. | 2 | | 050-099 |
| 804 | 20 | | PA | 4-9 | 21-61-71 | D13472 | | | 2 | | | | | GD01940 | D.. | 2 | | 150-155, 162-165, 275-276 |
| 804 | 20 | | PA | 3-3 | 21-61-71 | D13472 | | | 2 | | | | | GD01940 | D.. | 2 | | 156-157, 166-199, 277-278 |
| 804 | 20 | | PA | 4-0 | 21-61-71 | D13472 | | | 2 | | | | | GD01940 | D.. | 2 | | 280-299 |
| 805 | 24 | | PK | 4-0 | 21-61-71 | D13472 | | | 1 | | | | | SM00006 | | S | | 050-099 |
| 805 | 22 | | PA | 2-9 | 21-61-71 | D13472 | | | 1 | | | | | SM00006 | | S | | 150-155, 162-165 |
| 805 | 22 | | PA | 1-4 | 21-61-71 | D13472 | | | 1 | | | | | SM00006 | | S | | 156-157, 166-199 |
| 805 | 24 | | PK | 2-9 | 21-61-71 | D13472 | | | 1 | | | | | SM00006 | | S | | 275-276 |
| 805 | 24 | | PK | 1-4 | 21-61-71 | D13472 | | | 1 | | | | | SM00006 | | S | | 277-278 |
| 805 | 24 | | PK | 2-0 | 21-61-71 | D13472 | | | 1 | | | | | SM00006 | | S | | 280-299 |
| 806 | 24 | | PK | 59-0 | 33-21-31 | D05144P | | | 13 | | | | | D05138P | 4 | | | 050-099 |
| 806 | 24 | | PK | 68-3 | 33-21-31 | D05138P | | | 4 | | | | | D05144P | 13 | | | 150-199 |
| 814 | 20 | | PA | 58-0 | SPARE | D05138P | | | 14 | | | | | D05144P | 12 | | | 050-099 |
| 814 | 20 | | PA | 68-3 | SPARE | D05138P | | | 14 | | | | | D05144P | 12 | | | 150-199, 275-278 |
| 814 | 20 | | PA | 69-0 | SPARE | D05138P | | | 14 | | | | | D05144P | 12 | | | 280-299 |
| W1236 | 286T1236 | | | RIGHT MID ATTEND WORK LTS AND NIGHT LTS | | | | | | | | | | | | | | |
| 001 | 18 | | PA | 5-0 | 33-22-31 | D06028J | | | 3 | DK | | | | GD04198 | A.. | 2 | | 275-299 |
| 002 | 18 | | PA | 3-0 | 33-22-31 | D06188J | | | 4 | DK | | | | D06028J | 4 | DK | | 050-099, 275-299 |
| 002 | 18 | | PA | 1-6 | 33-22-31 | D06188J | | | 4 | DK | | | | D06028J | 4 | DK | | 150-199 |
| 003 | 18 | | PA | 3-0 | 33-22-31 | D06188J | | | 2 | DK | | | | D06028J | 2 | DK | | 050-099, 275-299 |
| 003 | 18 | | PA | 1-6 | 33-22-31 | D06188J | | | 2 | DK | | | | D06028J | 2 | DK | | 150-199 |
| 005 | 18 | | PA | 37-0 | 33-22-31 | D06188J | | | 1 | DK | | | | D05150P | 4 | DK | | 050-099 |
| 005 | 18 | | PA | 25-1 | 33-22-31 | D06188J | | | 1 | DK | | | | D05150P | 4 | DK | | 150-199 |
| 005 | 18 | | PA | 36-0 | 33-22-31 | D06188J | | | 1 | DK | | | | D05150P | 23 | DK | | 275-278 |
| 005 | 18 | | PA | 64-0 | 33-22-31 | D06188J | | | 1 | DK | | | | D05148P | 22 | DL | | 280-299 |
| 007 | 22 | | PA | 19-0 | 33-21-21 | D05148P | | | 1 | | | | | D06096J | =1 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|----------|---------|--------|--------|---------------------------|---------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1236 | 286T1236 | | | RIGHT MID ATTEND WORK LTS AND NIGHT LTS (continued) | | | | | | | | | | | | |
| 009 | 20 | | PA | | 4-0 | 33-21-21 | D06102P | | = | 1 | GD00938 | A.. | 2 | | 275-299 | |
| 011 | 18 | | PA | | 7-0 | 33-22-31 | D06188J | | 3 | DK | GD04198 | A.. | 2 | | 050-099 | |
| 011 | 18 | | PA | | 4-0 | 33-22-31 | D06188J | | 3 | DK | GD01950 | A.. | 2 | | 150-199 | |
| 011 | 18 | | PA | | 5-0 | 33-22-31 | D06188J | | 3 | DK | GD04198 | A.. | 2 | | 275-299 | |
| 012 | 22 | | PA | | 70-0 | 33-21-21 | D05148P | | 2 | | D05150P | | 1 | | 050-099 | |
| 012 | 22 | | PA | | 80-7 | 33-21-21 | D05148P | | 2 | | D05150P | | 1 | | 150-199, 275-278 | |
| 012 | 22 | | PA | | 80-0 | 33-21-21 | D05148P | | 2 | | D05150P | | 1 | | 280-299 | |
| 013 | 22 | | PA | | 90-0 | 33-21-21 | D05148P | | 3 | | L00461 | =P | C | * | 050-099 | |
| 013 | 22 | | PA | | 48-0 | 33-21-21 | D05148P | | 3 | | L00808 | =P | C | * | 150-199 | |
| 013 | 22 | | PA | | 48-0 | 33-21-21 | D05148P | | 34 | | L00808 | =P | C | | 275-278 | |
| 013 | 22 | | PA | | 49-0 | 33-21-21 | D05148P | | 34 | | STA0675R | REF | * | | 280-299 | |
| 015 | 22 | | PA | | 62-0 | 33-21-21 | D05148P | | 3 | | L00459 | =P | C | | 275-299 | |
| 017 | 22 | | PA | | 37-0 | 33-21-21 | D05148P | | 5 | | L00458 | =P | C | * | 050-099 | |
| 017 | 22 | | PA | | 36-0 | 33-21-21 | D05148P | | 5 | | L00458 | =P | C | * | 150-199 | |
| 017 | 22 | | PA | | 35-0 | 33-21-21 | D05148P | | 5 | | L00458 | =P | C | * | 275-299 | |
| 019 | 20 | | PA | | 12-0 | 33-21-21 | L00459 | | = | G | C | A.. | E | | 275-278 | |
| 019 | 20 | | PA | | 9-0 | 33-21-21 | L00459 | | = | G | C | GD00942 | A.. | E | 280-299 | |
| 020 | 22 | | PA | | 71-0 | 33-51-11 | D05148P | | 10 | | D05150P | | 10 | | 050-099 | |
| 020 | 22 | | PA | | 80-7 | 33-51-11 | D05148P | | 10 | | D05150P | | 10 | | 150-199, 275-278 | |
| 020 | 22 | | PA | | 80-0 | 33-51-11 | D05148P | | 10 | | D05150P | | 10 | | 280-299 | |
| 021 | 20 | | PA | | 6-0 | 33-21-21 | L00461 | | = | G | C | A.. | E | | 050-099 | |
| 021 | 20 | | PA | | 11-0 | 33-21-21 | L00461 | | = | G | C | GD04888 | A.. | E | 150-199 | |
| 021 | 20 | | PA | | 6-0 | 33-21-21 | L00461 | | = | G | C | GD04916 | A.. | E | 275-299 | |
| 023 | 20 | | PA | | 7-0 | 33-21-21 | L00458 | | = | G | C | GD01006 | A.. | E | 050-099, 150-199, 275-278 | |
| 023 | 20 | | PA | | 6-0 | 33-21-21 | L00458 | | = | G | C | GD01006 | A.. | E | 280-299 | |
| 025 | 22 | | PA | | 23-0 | 33-21-21 | L00461 | | = | P | C | * | L00462 | =P | C | 050-099 |
| 025 | 22 | | PA | | 14-3 | 33-21-21 | L00461 | | = | P | C | D05150P | | 2 | 150-199 | |
| 025 | 22 | | PA | | 18-1 | 33-21-21 | L00461 | | = | P | C | D05150P | | 2 | 275-278 | |
| 025 | 22 | | PA | | 18-0 | 33-21-21 | L00461 | | = | P | C | D05150P | | 2 | 280-299 | |
| 026 | 20 | | PA | | 70-0 | 33-22-42 | D05148P | | 14 | | D05150P | | 7 | | 050-099 | |
| 026 | 20 | | PA | | 80-7 | 33-22-42 | D05148P | | 14 | | D05150P | | 7 | | 150-199, 275-278 | |
| 026 | 20 | | PA | | 80-0 | 33-22-42 | D05148P | | 14 | | D05150P | | 7 | | 280-299 | |
| 027 | 20 | | PA | | 70-0 | 33-22-11 | D05148P | | 8 | | D05150P | | 8 | | 050-099 | |
| 027 | 20 | | PA | | 80-7 | 33-22-11 | D05148P | | 8 | | D05150P | | 8 | | 150-199, 275-278 | |
| 027 | 20 | | PA | | 80-0 | 33-22-11 | D05148P | | 8 | | D05150P | | 8 | | 280-299 | |
| 028 | 24 | | PK | | 70-0 | 33-22-11 | D05148P | | 9 | | D05150P | | 9 | | 050-099 | |
| 028 | 24 | | PK | | 80-7 | 33-22-11 | D05148P | | 9 | | D05150P | | 9 | | 150-199, 275-278 | |
| 028 | 24 | | PK | | 80-0 | 33-22-11 | D05148P | | 9 | | D05150P | | 9 | | 280-299 | |

WIRE LIST
D280T132

91-21-11
Section W1230
Page 17
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|--------|-------|------|----------|--------|-------------|---|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1236 | 286T1236 | | | RIGHT MID ATTEND WORK LTS AND NIGHT LTS (continued) | | | | | | | | | | | | | |
| 029 | 24 | | PK | 70-0 | 33-22-11 | D05148P | | 11 | | | | | D05150P | 11 | | | 050-099 |
| 029 | 24 | | PK | 80-7 | 33-22-11 | D05148P | | 11 | | | | | D05150P | 11 | | | 150-199, 275-278 |
| 029 | 24 | | PK | 80-0 | 33-22-11 | D05148P | | 11 | | | | | D05150P | 11 | | | 280-299 |
| 030 | 24 | | PK | 70-0 | 33-22-11 | D05148P | | 12 | | | | | D05150P | 12 | | | 050-099 |
| 030 | 24 | | PK | 80-7 | 33-22-11 | D05148P | | 12 | | | | | D05150P | 12 | | | 150-199, 275-278 |
| 030 | 24 | | PK | 80-0 | 33-22-11 | D05148P | | 12 | | | | | D05150P | 12 | | | 280-299 |
| 031 | 22 | | PA | 51-0 | 21-61-31 | D05148P | | 4 | | | | | D03826 | 1 | | | 050-099 |
| 031 | 22 | | PA | 60-0 | 21-61-31 | D05148P | | 4 | | | | | D03826 | 1 | | | 150-199 |
| 031 | 22 | | PA | 65-0 | 21-61-31 | D05148P | | 4 | | | | | D03826 | 1 | | | 275-278 |
| 031 | 22 | | PA | 62-0 | 21-61-31 | D05148P | | 4 | | | | | D03826 | 1 | | | 280-299 |
| 032 | 20 | | PA | 4-0 | 21-61-31 | D03826 | | 2 | | | | | GD01940 | D.. | 2 | | ALL |
| 033 | 20 | | PA | 1-0 | 21-65-11 | SM00001 | | | | S | | | D03994 | B | | | ALL |
| 034 | 20 | | PA | 3-0 | 21-65-11 | SM00001 | | | | S | | | GD01940 | D.. | 2 | | 050-099, 150-199, 275-278 |
| 034 | 20 | | PA | 4-0 | 21-65-11 | SM00001 | | | | S | | | GD01940 | D.. | 2 | | 280-299 |
| 037 | 22 | | PA | 84-0 | SPARE | D05148P | | 15 | | | | | STA0798L | REF | Y | | 280-299 |
| 039 | 22 | | PA | 84-0 | SPARE | D05148P | | 17 | | | | | STA0798L | CAP | Y | | 280-299 |
| 040 | 22 | | PA | 70-0 | 33-27-11 | D05148P | | 19 | | | | | D05150P | 3 | | | 050-099 |
| 040 | 22 | | PA | 80-7 | 33-27-11 | D05148P | | 19 | | | | | D05150P | 3 | | | 150-199, 275-278 |
| 040 | 22 | | PA | 80-0 | 33-27-11 | D05148P | | 19 | | | | | D05150P | 3 | | | 280-299 |
| 041 | 20 | | PA | 6-0 | 33-21-21 | L00457 | | =G | C | | | | GD01010 | A.. | E | | ALL |
| 044 | 22 | | PA | 28-0 | 33-21-21 | L00457 | | =P | C | | | | L00458 | =P | C | * | 050-099 |
| 044 | 22 | | PA | 21-0 | 33-21-21 | L00457 | | =P | C | | | | L00458 | =P | C | * | 150-199, 275-299 |
| 045 | 22 | | PA | 70-0 | 33-22-42 | D05148P | | 25 | | | | | D05150P | 24 | | | 050-099 |
| 045 | 22 | | PA | 80-7 | 33-22-42 | D05148P | | 25 | | | | | D05150P | 24 | | | 150-199, 275-278 |
| 045 | 22 | | PA | 80-0 | 33-22-42 | D05148P | | 25 | | | | | D05150P | 24 | | | 280-299 |
| 058 | 22 | | PA | 80-0 | 33-22-42 | D05148P | | 53 | | | | | D05150P | 6 | | | 280-299 |
| 064 | 20 | | PA | 7-0 | 33-21-21 | L00808 | | =G | C | | | | GD04976 | A.. | E | | 150-199, 275-278 |
| 064 | 20 | | PA | 5-0 | 33-21-21 | STA0675R | | REF | * | | | | GD04976 | A.. | E | | 280-299 |
| 123 | 20 | | PA | 84-0 | 33-24-14 | D05148P | | 41 | | | | | SP03492 | | S | | 275-299 |
| 129 | 20 | | PA | 84-0 | 33-24-14 | D05148P | | 40 | | | | | SP03490 | | S | | 275-299 |
| 147 | 22 | | PA | 28-0 | 33-21-21 | L00458 | | =P | C | * | | | L00459 | =P | C | | 050-099 |
| 147 | 22 | | PA | 26-0 | 33-21-21 | L00459 | | =P | C | | | | L00808 | =P | C | * | 150-199 |
| 148 | 20 | | PA | 6-0 | 33-21-21 | L00459 | | =G | C | | | | GD00942 | A.. | E | | 050-099 |
| 148 | 20 | | PA | 6-0 | 33-21-21 | L00459 | | =G | C | | | | GD05304 | A.. | E | | 150-199 |
| 149 | 18 | | PA | 7-0 | 33-22-31 | D06028J | | 3 | DK | | | | GD04198 | A.. | 2 | | 050-099 |
| 149 | 18 | | PA | 4-0 | 33-22-31 | D06028J | | 3 | DK | | | | GD01950 | A.. | 2 | | 150-199 |
| 150 | 20 | | PA | 6-0 | 33-22-42 | D06028J | | 5 | | | | | GD01950 | A.. | 2 | | 150-199 |
| 151 | 20 | | PA | 25-3 | 33-22-42 | D06028J | | 1 | | | | | D05150P | 23 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 18

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1236 | 286T1236 | | | RIGHT MID ATTEND WORK LTS AND NIGHT LTS (continued) | | | | | | | | | | | |
| 152 | 20 | PA | | 1-0 | 21-65-11 | D13476 | | B | | | SM00007 | | S | | ALL |
| 154 | 22 | PA | | 80-7 | 33-22-42 | D05148P | | 46 | | | D05150P | 22 | | | 275-278 |
| 154 | 22 | PA | | 80-0 | 33-22-42 | D05148P | | 46 | | | D05150P | 22 | | | 280-299 |
| 155 | 20 | PA | | 3-0 | 21-65-11 | SM00007 | | | S | | GD01940 | D.. | 2 | | 050-099 |
| 155 | 20 | PA | | 4-0 | 21-65-11 | GD01940 | | | D.. | 2 | SM00007 | | S | | 150-155, 162-165, 275-276, 280-299 |
| 155 | 20 | PA | | 3-0 | 21-65-11 | GD01940 | | | D.. | 2 | SM00007 | | S | | 156-157, 166-199, 277-278 |
| 156 | 20 | PA | | 80-7 | 33-22-42 | D05148P | | 44 | | | D05150P | 20 | | | 275-278 |
| 156 | 20 | PA | | 80-0 | 33-22-42 | D05148P | | 44 | | | D05150P | 20 | | | 280-299 |
| 157 | 20 | PA | | 80-7 | 33-22-42 | D05148P | | 45 | | | D05150P | 21 | | | 275-278 |
| 157 | 20 | PA | | 80-0 | 33-22-42 | D05148P | | 45 | | | D05150P | 21 | | | 280-299 |
| 162 | 22 | PA | | 26-0 | 33-21-21 | D05148P | | 22 | | | L01180 | =P | C | | 050-099 |
| 162 | 22 | PA | | 27-0 | 33-21-21 | D05148P | | 22 | | | L01180 | =P | C | | 162-199 |
| 163 | 20 | PA | | 14-0 | 33-21-21 | L01180 | | =G | C | | GD00938 | A.. | 2 | | 050-099 |
| 163 | 20 | PA | | 16-0 | 33-21-21 | L01180 | | =G | C | | GD00938 | A.. | 2 | | 162-199 |
| 164 | 20 | PA | | 7-0 | 33-21-21 | L00462 | | =G | C | | GD01018 | A.. | E | | 050-099 |
| 165 | 24 | PK | | 21-0 | 33-21-31 | D06900P | | 5 | | | D05148P | 43 | | | 050-099 |
| 165 | 24 | PK | | 20-0 | 33-21-31 | D06900P | | 5 | | | D05148P | 43 | | | 162-199 |
| 166 | 20 | PA | | 5-0 | 33-21-31 | D06900P | | 6 | | | GD00938 | A.. | 2 | | 050-099 |
| 166 | 20 | PA | | 6-0 | 33-21-31 | D06900P | | 6 | | | GD00938 | A.. | 2 | | 162-199 |
| 167 | 24 | PK | | 21-0 | 33-21-31 | D06900P | | 7 | | | D05148P | 44 | | | 050-099 |
| 167 | 24 | PK | | 20-0 | 33-21-31 | D06900P | | 7 | | | D05148P | 44 | | | 162-199 |
| 168 | 20 | PA | | 21-0 | 26-13-12 | D06900P | | 3 | | | D05148P | 24 | | | 050-099 |
| 168 | 20 | PA | | 20-0 | 26-13-12 | D06900P | | 3 | | | D05148P | 24 | | | 162-163 |
| 168 | 20 | PA | | 20-0 | 26-13-12 | SM00008 | | | S | | D05148P | 24 | | | 164-199 |
| 169 | 20 | PA | | 21-0 | 26-13-12 | D06900P | | 4 | | | D05148P | 6 | | | 050-099 |
| 169 | 20 | PA | | 20-0 | 26-13-12 | D06900P | | 4 | | | D05148P | 6 | | | 162-199 |
| 170 | 20 | PA | | 21-0 | 26-13-12 | D06900P | | 2 | | | D05148P | 15 | | | 050-099 |
| 170 | 20 | PA | | 20-0 | 26-13-12 | D06900P | | 2 | | | D05148P | 15 | | | 162-199 |
| 171 | 20 | PA | | 21-0 | 26-13-12 | D06900P | | 1 | | | D05148P | 17 | | | 050-099 |
| 171 | 20 | PA | | 20-0 | 26-13-12 | D06900P | | 1 | | | D05148P | 17 | | | 162-199 |
| 183 | 20 | PA | | 21-0 | 26-13-12 | D06900P | | 8 | | | D05148P | 55 | | | 050-099 |
| 183 | 20 | PA | | 20-0 | 26-13-12 | D06900P | | 8 | | | D05148P | 55 | | | 162-199 |
| 184 | 22 | PA | | 24-0 | 21-66-21 | D13920 | | 31 | | | D05148P | 26 | | | 050-099, 162-199 |
| 185 | 22 | PA | | 24-0 | 21-66-21 | D13920 | | 18 | | | D05148P | 27 | | | 050-099, 162-199 |
| 188 | 22 | PA | | 1-0 | 21-66-21 | D13920 | | 15 | | | D13920 | 16 | | | 050-099, 162-199 |
| 189 | 20 | PA | | 8-0 | 21-66-21 | D13920 | | 13 | | | GD01918 | D.. | 2 | | 050-099 |
| 189 | 20 | PA | | 9-0 | 21-66-21 | D13920 | | 13 | | | GD01918 | D.. | 2 | | 162-199 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 19

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1236 | 286T1236 | | | RIGHT MID ATTEND WORK LTS AND NIGHT LTS (continued) | | | | | | | | | | | | | |
| 190 | 20 | | PA | 8-0 | 21-66-21 | D13920 | | 60 | | | | | GD01918 | S.. | 2 | | 050-099 |
| 190 | 20 | | PA | 9-0 | 21-66-21 | D13920 | | 60 | | | | | GD01918 | S.. | 2 | | 162-199 |
| 191 | 20 | | PA | 8-0 | 21-66-21 | D13918 | | 23 | | | | | GD01918 | S.. | 2 | | 050-099, 162-199 |
| 192 | 22 | | PA | 21-0 | 21-66-21 | D05148P | | 40 | | | | | D06900P | | 9 | | 050-099 |
| 192 | 22 | | PA | 20-0 | 21-66-21 | D05148P | | 40 | | | | | D06900P | | 9 | | 162-199 |
| 193 | 22 | | PA | 21-0 | 21-66-21 | D05148P | | 41 | | | | | D06900P | | 11 | | 050-099 |
| 193 | 22 | | PA | 20-0 | 21-66-21 | D05148P | | 41 | | | | | D06900P | | 11 | | 162-199 |
| 194 | 22 | | PA | 24-0 | 21-66-21 | D13920 | | 29 | | | | | D05148P | | 34 | | 050-099 |
| 194 | 22 | | PA | 24-0 | 21-66-21 | D05148P | | 34 | | | | | D13920 | | 29 | | 162-199 |
| 195 | 22 | | PA | 24-0 | 21-66-21 | D13920 | | 32 | | | | | D05148P | | 35 | | 050-099 |
| 195 | 22 | | PA | 24-0 | 21-66-21 | D05148P | | 35 | | | | | D13920 | | 32 | | 162-199 |
| 197 | 22 | | PA | 24-0 | 21-66-21 | D13920 | | 33 | | | | | D05148P | | 36 | | 050-099 |
| 197 | 22 | | PA | 24-0 | 21-66-21 | D05148P | | 36 | | | | | D13920 | | 33 | | 162-199 |
| 198 | 22 | | PA | 70-0 | 21-66-31 | D05148P | | 42 | | | | | D05150P | | 13 | | 050-099 |
| 198 | 22 | | PA | 80-7 | 21-66-31 | D05148P | | 42 | | | | | D05150P | | 13 | | 150, 152-199 |
| 199 | 22 | | PA | 70-0 | 21-66-31 | D05148P | | 16 | | | | | D05150P | | 14 | | 050-099 |
| 199 | 22 | | PA | 80-7 | 21-66-31 | D05148P | | 16 | | | | | D05150P | | 14 | | 150, 152-199 |
| 200B | 22 | | PB HY | 7-0 | 21-66-21 | D13920 | | 3 | | | | | D13882 | | 1 | | 050-099 |
| 200B | 22 | | PB HY | 8-0 | 21-66-21 | D13920 | | 3 | | | | | D13882 | | 1 | | 162-199 |
| 200R | 22 | | PB HY | 0-0 | 21-66-21 | D13920 | | 4 | | | | | D13882 | | 3 | | 050-099, 162-199 |
| 201B | 20 | | PB A | 51-0 | 21-65-11 | D05148P | | 7 | | | | | D03994 | | A | | 050-099 |
| 201B | 20 | | PB IA | 60-0 | 21-65-11 | D05148P | | 7 | | | | | D03994 | | A | | 150-199 |
| 201B | 20 | | PB A | 64-0 | 21-65-11 | D05148P | | 7 | | | | | D03994 | | A | | 275-278 |
| 201B | 20 | | PB A | 62-0 | 21-65-11 | D05148P | | 7 | | | | | D03994 | | A | | 280-299 |
| 201R | 20 | | PB A | 0-0 | 21-65-11 | D05148P | | 13 | | | | | SM00001 | | S | | 050-099, 275-299 |
| 201R | 20 | | PB IA | 0-0 | 21-65-11 | D05148P | | 13 | | | | | SM00001 | | S | | 150-199 |
| 202B | 24 | | PL B | 51-0 | 21-61-31 | D05148P | | 21 | | | | | D03982 | | 1 | | 050-099 |
| 202B | 24 | | PL B | 60-0 | 21-61-31 | D05148P | | 21 | | | | | D03982 | | 1 | | 150-199 |
| 202B | 24 | | PL B | 65-0 | 21-61-31 | D05148P | | 21 | | | | | D03982 | | 1 | | 275-278 |
| 202B | 24 | | PL B | 62-0 | 21-61-31 | D05148P | | 21 | | | | | D03982 | | 1 | | 280-299 |
| 202R | 24 | | PL B | 0-0 | 21-61-31 | D05148P | | 23 | | | | | D03982 | | 2 | | ALL |
| 203B | 20 | | PB IC | 51-0 | 21-65-11 | D05148P | | 18 | | | | | D13476 | | A | | 050-099 |
| 203B | 20 | | PB IC | 60-0 | 21-65-11 | D05148P | | 18 | | | | | D13476 | | A | | 150-199, 275-278 |
| 203B | 20 | | PB IC | 62-0 | 21-65-11 | D05148P | | 18 | | | | | D13476 | | A | | 280-299 |
| 203R | 20 | | PB IC | 0-0 | 21-65-11 | D05148P | | 31 | | | | | SM00007 | | S | | ALL |
| 205B | 24 | | PL IE | 51-0 | 21-61-71 | D13468 | | 1 | | | | | D05148P | | 32 | | 050-099 |
| 205B | 24 | | PL IE | 60-0 | 21-61-71 | D05148P | | 32 | | | | | D13468 | | 1 | | 150-199, 275-299 |
| 205R | 24 | | PL IE | 0-0 | 21-61-71 | D13468 | | 2 | | | | | D05148P | | 33 | | 050-099 |
| 205R | 24 | | PL IE | 0-0 | 21-61-71 | D05148P | | 33 | | | | | D13468 | | 2 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1230

Page 20

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1236 | 286T1236 | | | RIGHT MID ATTEND WORK LTS AND NIGHT LTS (continued) | | | | | | | | | | | |
| 206B | 22 | PB | IF | | 14-0 | 21-66-21 | D13920 | | | 5 | D13880 | | | 1 | 050-099 |
| 206B | 22 | PB | IF | | 15-0 | 21-66-21 | D13920 | | | 5 | D13880 | | | 1 | 162-199 |
| 206R | 22 | PB | IF | | 0-0 | 21-66-21 | D13920 | | | 6 | D13880 | | | 2 | 050-099, 162-199 |
| 207 | 20 | UA | | | 8-0 | 21-66-21 | D13918 | | | | GD01918 | S.. | 2 | | 050-099, 162-199 |
| 207B | 22 | PR | IG | | 24-0 | 21-66-21 | D13918 | | | 22 | D05148P | | | 39 | 050-099 |
| 207B | 22 | PR | IG | | 23-0 | 21-66-21 | D13918 | | | 22 | D05148P | | | 39 | 162-199 |
| 207R | 22 | PR | IG | | 0-0 | 21-66-21 | D13918 | | | 21 | D05148P | | | 38 | 050-099, 162-199 |
| 207Z | | | IG | | 0-0 | 21-66-21 | D13918 | | | | D05148P | FA | | 37 | 050-099, 162-199 |
| 300B | 22 | PC | LY | | 16-0 | 21-66-21 | D13920 | | | 8 | D13886 | | | A | 050-099 |
| 300B | 22 | PC | LY | | 20-0 | 21-66-21 | D13920 | | | 8 | D13886 | | | A | 162-199 |
| 300R | 22 | PC | LY | | 0-0 | 21-66-21 | D13920 | | | 9 | D13886 | | | B | 050-099, 162-199 |
| 300Y | 22 | PC | LY | | 0-0 | 21-66-21 | D13920 | | | 10 | D13886 | | | C | 050-099, 162-199 |
| 500 | 22 | PA | | | 70-0 | 21-66-41 | D05148P | | | 28 | D05150P | | | 15 | 050-099 |
| 500 | 22 | PA | | | 80-7 | 21-66-41 | D05148P | | | 28 | D05150P | | | 15 | 150, 152-199 |
| 501 | 22 | PA | | | 70-0 | 21-66-41 | D05148P | | | 29 | D05150P | | | 16 | 050-099 |
| 501 | 22 | PA | | | 80-7 | 21-66-41 | D05148P | | | 29 | D05150P | | | 16 | 150, 152-199 |
| 502 | 22 | PA | | | 1-0 | 21-66-21 | D13920 | | | 43 | D13920 | | | 48 | 050-099, 162-199 |
| 504 | 20 | PA | | | 6-0 | 26-13-12 | D13950 | | | = 1 | SM00008 | | | S | 164-199 |
| 505 | 20 | PA | | | 11-0 | 26-13-12 | D13928 | | | = 1 | D06900P | | | 12 | 164-199 |
| 506 | 20 | PA | | | 10-0 | 26-13-12 | D06900P | | | 3 | SM00008 | | | S | 164-199 |

WIRE LIST
D280T132

91-21-11
Section W1230
Page 21 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1240 | 286T1240 | | | RIGHT AFT ATTEND WORK LTS NT LTS | | | | | | | | | | | |
| 001 | 24 | | PK | | 73-0 | 33-21-21 | D05154P | | 4 | | D01650 | | 31 | | 050-099 |
| 001 | 24 | | PK | | 83-0 | 33-21-21 | D05154P | | 4 | | D01650 | | 31 | | 150-199, 275-299 |
| 002 | 20 | | PA | | 10-0 | 33-21-21 | GD00054 | A.. | 2 | | D01650 | | 32 | | 050-099 |
| 002 | 20 | | PA | | 8-0 | 33-21-21 | GD00054 | A.. | 2 | | D01650 | | 32 | | 150-199 |
| 002 | 20 | | PA | | 18-0 | 33-21-21 | GD00070 | A.. | 2 | | D01650 | | 32 | | 275-299 |
| 003 | 20 | | PA | | 6-0 | 33-21-21 | L00463 | =G | C | | GD01028 | A.. | E | | 050-099 |
| 003 | 20 | | PA | | 6-0 | 33-21-21 | L00463 | =G | C | | GD04928 | A.. | E | | 150-199, 275-299 |
| 004 | 18 | | PA | | 22-0 | 33-22-31 | D10176 | | 3 | DK | GD00932 | A.. | 2 | | 275-299 |
| 005 | 20 | | PA | | 6-0 | 33-21-21 | L00465 | =G | C | | GD01032 | A.. | E | | 050-099 |
| 005 | 20 | | PA | | 6-0 | 33-21-21 | L00465 | =G | C | | GD01528 | A.. | E | | 150-199, 275-299 |
| 006 | 18 | | PA | | 23-0 | 33-22-31 | D01650 | | 16 | FM | L00189 | =P | C | | 050-099 |
| 006 | 18 | | PA | | 24-0 | 33-22-31 | D01650 | | 16 | DK | L00189 | =P | C | | 150-199 |
| 006 | 18 | | PA | | 26-0 | 33-22-31 | D10176 | | 2 | DK | L00188 | =P | C | | 275-299 |
| 008 | 22 | | PA | | 29-0 | 33-21-21 | L00465 | =P | C | | L00463 | =P | C | * | 050-099 |
| 008 | 22 | | PA | | 25-0 | 33-21-21 | L00810 | =P | C | | L00463 | =P | C | * | 150-199, 275-299 |
| 012 | 22 | | PA | | 20-0 | 33-21-21 | D05154P | | 2 | | L00463 | =P | C | * | 050-099 |
| 012 | 22 | | PA | | 23-0 | 33-21-21 | D05154P | | 2 | | L00463 | =P | C | * | 150-199, 275-299 |
| 014 | 22 | | PA | | 25-0 | 33-21-21 | L00810 | =P | C | * | L00465 | =P | C | | 150-199, 275-299 |
| 015 | 18 | | PA | | 87-0 | 33-22-31 | D10176 | | 1 | DK | D05154P | | 1 | | 275-278 |
| 015 | 18 | | PA | | 49-0 | 33-22-31 | SM00008 | | | S | D05154P | | 1 | | 280-299 |
| 016 | 18 | | PA | | 24-0 | 33-22-31 | L00188 | =P | C | | D10176 | 2 | DK | | 050-099 |
| 016 | 18 | | PA | | 25-0 | 33-22-31 | L00188 | =P | C | | D10176 | 2 | DK | | 150-199 |
| 016 | 18 | | PA | | 24-0 | 33-22-31 | L00189 | =P | C | | D01650 | 16 | DK | | 275-299 |
| 017 | 18 | | PA | | 13-0 | 33-22-31 | GD00070 | A.. | 2 | | L00188 | =G | C | | 050-099 |
| 017 | 18 | | PA | | 12-0 | 33-22-31 | GD00070 | A.. | 2 | | L00188 | =G | C | | 150-199 |
| 017 | 18 | | PA | | 10-0 | 33-22-31 | GD00070 | A.. | 2 | | L00189 | =G | C | | 275-299 |
| 018 | 18 | | PA | | 10-0 | 33-22-31 | GD00070 | A.. | 2 | | L00189 | =G | C | | 050-099, 150-199 |
| 018 | 18 | | PA | | 12-0 | 33-22-31 | GD00070 | A.. | 2 | | L00188 | =G | C | | 275-299 |
| 019 | 22 | | PA | | 72-0 | 33-22-42 | D05154P | | 3 | | D01650 | | 1 | | 050-099 |
| 019 | 22 | | PA | | 87-0 | 33-22-42 | D05154P | | 3 | | D01650 | | 1 | | 150-199, 275-299 |
| 020 | 24 | | PK | | 73-0 | 33-21-12 | D05154P | | 5 | | D01650 | | 7 | | 050-099 |
| 020 | 24 | | PK | | 83-0 | 33-21-12 | D05154P | | 5 | | D01650 | | 7 | | 150-199, 275-299 |
| 021 | 22 | | PA | | 73-0 | 33-22-42 | D05154P | | 6 | | D01650 | | 4 | | 050-099 |
| 021 | 22 | | PA | | 83-0 | 33-22-42 | D05154P | | 6 | | D01650 | | 4 | | 150-199, 275-299 |
| 022 | 22 | | PA | | 83-0 | 33-22-42 | D05154P | | 8 | | D01650 | | 8 | | 275-299 |
| 023 | 22 | | PA | | 83-0 | SPARE | D05154P | | 14 | | D01650 | | 5 | | 150-199, 275-299 |
| 024 | 18 | | PA | | 30-0 | 33-22-11 | L00186 | =P | C | | D01650 | 12 | DK | | 050-099 |
| 024 | 18 | | PA | | 29-0 | 33-22-11 | L00186 | =P | C | | D01650 | 12 | DK | | 150-199, 275-299 |
| 025 | 18 | | PA | | 83-0 | 33-22-11 | D05154P | | 21 | DL | D01650 | | 13 | DK | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1240

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1240 | 286T1240 | | | RIGHT AFT ATTEND WORK LTS NT LTS (continued) | | | | | | | | | | | |
| 026 | 18 | | PA | | 5-0 | 33-22-11 | L00186 | = G | C | | GD00932 | A.. | 2 | | 050-099 |
| 026 | 18 | | PA | | 8-0 | 33-22-11 | L00186 | = G | C | | GD00932 | A.. | 2 | | 150-199, 275-299 |
| 027 | 24 | | PK | | 73-0 | 33-22-11 | D05154P | | 7 | | D01650 | | 35 | | 050-099 |
| 027 | 24 | | PK | | 83-0 | 33-22-11 | D05154P | | 7 | | D01650 | | 35 | | 150-199, 275-299 |
| 028 | 18 | | PA | | 8-0 | 33-22-11 | GD00070 | A.. | 2 | | L00187 | = G | C | | 050-099 |
| 028 | 18 | | PA | | 6-0 | 33-22-11 | GD00070 | A.. | 2 | | L00187 | = G | C | | 150-199, 275-299 |
| 029 | 24 | | PK | | 43-0 | 33-22-11 | D05154P | | 11 | | SP01466 | | S | | 050-099 |
| 029 | 24 | | PK | | 53-0 | 33-22-11 | D05154P | | 11 | | SP01466 | | S | | 150-199, 275-299 |
| 030 | 24 | | PK | | 73-0 | 33-22-11 | D05154P | | 12 | | D01650 | | 36 | | 050-099 |
| 030 | 24 | | PK | | 84-0 | 33-22-11 | D05154P | | 12 | | D01650 | | 36 | | 150-199, 275-299 |
| 031 | 24 | | PK | | 38-0 | 33-22-11 | SP01466 | | | S | D01650 | | 34 | | ALL |
| 032 | 18 | | PA | | 18-0 | 33-22-11 | L00187 | = P | C | | D01650 | | 14 | DK | 050-099 |
| 032 | 18 | | PA | | 16-0 | 33-22-11 | L00187 | = P | C | | D01650 | | 14 | DK | 150-199, 275-299 |
| 033 | 22 | | PA | | 2-0 | 33-21-31 | SM00001 | | | S | D01650 | | 3 | | 050-099 |
| 033 | 22 | | PA | | 3-0 | 33-21-31 | SM00001 | | | S | D01650 | | 3 | | 150-199, 275-299 |
| 034 | 24 | | PK | | 73-0 | 33-21-31 | D05154P | | 10 | | D01650 | | 2 | | 050-099 |
| 034 | 24 | | PK | | 83-0 | 33-21-31 | D05154P | | 10 | | D01650 | | 2 | | 150-199, 275-299 |
| 035 | 20 | | PA | | 9-0 | 33-22-42 | GD00054 | A.. | 2 | | SM00001 | | S | | 050-099 |
| 035 | 20 | | PA | | 8-0 | 33-22-42 | GD00054 | A.. | 2 | | SM00001 | | S | | 150-199 |
| 035 | 20 | | PA | | 34-0 | 33-22-42 | GD04506 | A.. | 2 | | SM00001 | | S | | 275-299 |
| 036 | 22 | | PA | | 2-0 | 33-22-42 | D01650 | | 6 | | SM00001 | | S | | 050-099 |
| 036 | 22 | | PA | | 3-0 | 33-22-42 | D01650 | | 6 | | SM00001 | | S | | 150-199, 275-299 |
| 037 | 20 | | PA | | 6-0 | 33-21-21 | L00810 | = G | C | | GD04894 | A.. | E | | 150-199, 275-299 |
| 038 | 22 | | PA | | 3-0 | 33-22-42 | D01650 | | 10 | | SM00001 | | S | | 275-299 |
| 045 | 22 | | PA | | 73-0 | 33-27-11 | D05154P | | 26 | | D01650 | | 59 | | 050-099 |
| 045 | 22 | | PA | | 83-0 | 33-27-11 | D05154P | | 26 | | D01650 | | 59 | | 150-199 |
| 045 | 22 | | PA | | 53-0 | 33-27-11 | D05154P | | 26 | | SP00726 | | 9 | | 275-299 |
| 047 | 22 | | PA | | 73-0 | 33-27-11 | D05154P | | 25 | | D01650 | | 61 | | 050-099 |
| 047 | 22 | | PA | | 87-0 | 33-27-11 | D05154P | | 25 | | D01650 | | 61 | | 150-199 |
| 047 | 22 | | PA | | 53-0 | 33-27-11 | D05154P | | 25 | | SP00728 | | 9 | | 275-299 |
| 049 | 22 | | PA | | 73-0 | 33-51-11 | D01650 | | 37 | | D05154P | | 27 | | 050-099 |
| 049 | 22 | | PA | | 83-0 | 33-51-11 | D01650 | | 37 | | D05154P | | 27 | | 150-199, 275-299 |
| 050 | 20 | | PA | | 11-0 | 33-51-11 | D01650 | | 38 | | GD00054 | D.. | 2 | | 050-099 |
| 050 | 20 | | PA | | 8-0 | 33-51-11 | D01650 | | 38 | | GD00054 | D.. | 2 | | 150-199, 275-299 |
| 051 | 18 | | PA | | 11-0 | 33-51-11 | D01650 | | 11 | DK | GD00054 | A.. | 2 | | 050-099 |
| 051 | 18 | | PA | | 8-0 | 33-51-11 | D01650 | | 11 | DK | GD00054 | A.. | 2 | | 150-199, 275-299 |
| 057 | 24 | | PK | | 73-0 | 33-21-12 | D01650 | | 9 | | D05154P | | 31 | | 050-099 |
| 057 | 24 | | PK | | 83-0 | 33-21-12 | D01650 | | 9 | | D05154P | | 31 | | 150-199, 275-299 |
| 060 | 20 | | PA | | 1-0 | 33-24-14 | D05154P | | 17 | | SM00003 | | S | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1240

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1240 | 286T1240 | | | RIGHT AFT ATTEND WORK LTS NT LTS (continued) | | | | | | | | | | | | | |
| 061 | 20 | | PA | 1-0 | 33-24-14 | D05154P | | 18 | | | | | SM00004 | | S | | 050-099 |
| 072 | 18 | | PA | 33-0 | 33-22-31 | D10176 | | 4 | DK | | | | D12090 | = 1 | | | 050-099 |
| 072 | 18 | | PA | 36-0 | 33-22-31 | D12090 | | | | | | | D10176 | 4 | DK | | 150-199 |
| 072 | 18 | | PA | 41-0 | SPARE | D10176 | | 4 | DK | | | | SP05308 | | S | | 280-299 |
| 073 | 18 | | PA | 41-0 | 33-22-31 | D10176 | | 1 | DK | | | | SM00008 | | S | | 280-299 |
| 076 | 18 | | PA | 8-0 | 33-22-31 | D12092 | | | | | | | GD01126 | A.. | 2 | | 050-099, 150-199 |
| 077 | 22 | | PA | 63-0 | 33-24-12 | L00415 | | | NS | C | | | SM00003 | | S | | 050-099 |
| 078 | 22 | | PA | 63-0 | 33-24-12 | L00415 | | | FSB | C | | | SM00004 | | S | | 050-099 |
| 079 | 20 | | PA | 8-0 | 33-24-12 | L00415 | | | GND | C | | | GD00026 | A.. | 2 | | 050-099 |
| 080 | 22 | | PA | 49-0 | 33-24-14 | L00416 | | | NS | C | | | SM00003 | | S | | 050-099 |
| 081 | 22 | | PA | 49-0 | 33-24-14 | L00416 | | | FSB | C | | | SM00004 | | S | | 050-099 |
| 082 | 20 | | PA | 6-0 | 33-24-14 | L00416 | | | GND | C | | | GD00020 | A.. | 2 | | 050-099 |
| 093 | 22 | | PA | 53-0 | 33-21-21 | D05154P | | 39 | | | | | L01181 | =P | C | | 050-099 |
| 093 | 22 | | PA | 64-0 | 33-21-21 | D05154P | | 39 | | | | | L01181 | =P | C | | 162-199 |
| 094 | 20 | | PA | 14-0 | 33-21-21 | L01181 | | | =G | C | | | GD01036 | A.. | E | | 050-099, 162-199 |
| 120 | 20 | | PA | 10-0 | 33-27-11 | D01650 | | 60 | | | | | GD00054 | A.. | 2 | | 050-099 |
| 120 | 20 | | PA | 8-0 | 33-27-11 | GD00054 | | | A.. | 2 | | | D01650 | 60 | | | 150-199 |
| 122 | 24 | | PK | 73-0 | 33-21-12 | D01650 | | 20 | | | | | D05154P | 37 | | | 050-099 |
| 122 | 20 | | PA | 83-0 | 33-21-12 | D01650 | | 20 | | | | | D05154P | 37 | | | 150-199 |
| 123 | 24 | | PK | 73-0 | 33-21-12 | D01650 | | 19 | | | | | D05154P | 36 | | | 050-099 |
| 123 | 24 | | PK | 83-0 | 33-21-12 | D01650 | | 19 | | | | | D05154P | 36 | | | 150-199 |
| 124 | 18 | | PA | 76-0 | 33-22-31 | D10176 | | 1 | DK | | | | D05154P | 1 | | | 050-099 |
| 124 | 18 | | PA | 88-0 | 33-22-31 | D05154P | | 1 | | | | | D10176 | 1 | DK | | 150-199 |
| 125 | 20 | | PA | 18-0 | 33-22-31 | D10176 | | 3 | | | | | GD00932 | A.. | 2 | | 050-099 |
| 125 | 20 | | PA | 31-0 | 33-22-31 | GD01876 | | | A.. | G | | | D10176 | 3 | DK | | 150-164 |
| 125 | 20 | | PA | 22-0 | 33-22-31 | GD00932 | | | A.. | 2 | | | D10176 | 3 | DK | | 165-199 |
| 132 | 18 | | PA | 13-0 | 33-22-31 | D07086J | | 1 | DK | | | | SM00008 | | S | | 280-299 |
| 133 | 18 | | PA | 24-0 | 33-22-31 | D07086J | | 2 | DK | | | | D07084J | 2 | DK | | 280-299 |
| 134 | 18 | | PA | 20-0 | 33-22-31 | D07086J | | 3 | DK | | | | GD01036 | A.. | E | | 280-299 |
| 135 | 18 | | PA | 24-0 | 33-22-31 | D07086J | | 4 | DK | | | | D07084J | 4 | DK | | 280-299 |
| 136 | 18 | | PA | 37-0 | SPARE | D01650 | | 17 | DK | | | | SP05306 | | S | | 280-299 |
| 137 | 18 | | PA | 12-0 | 33-22-31 | D07084J | | 3 | DK | | | | GD01036 | A.. | E | | 280-299 |
| 600 | 18 | | PA | 73-0 | 33-22-11 | D01650 | | 13 | DK | | | | D05154P | 21 | DL | | 050-099 |
| 600 | 18 | | PA | 83-0 | 33-22-11 | D05154P | | 21 | DL | | | | D01650 | 13 | DK | | 150-199 |
| W1246 | 286T1246 | | | HYDRAULICS SYSTEM,W/W | | | | | | | | | | | | | |
| 001 | 22 | | PA | 79-0 | 29-31-11 | D05732P | | 1 | | | | | D05510J | 7 | | | 050-099 |
| 001 | 22 | | PA | 88-0 | 29-31-11 | D05732P | | 1 | | | | | D05510J | 7 | | | 150-199, 275-299 |
| 004 | 22 | | PA | 79-0 | 29-21-32 | D05732P | | 4 | | | | | D05510J | 2 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1240

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1246 | 286T1246 | | | HYDRAULICS SYSTEM,W/W (continued) | | | | | | | | | | | |
| 004 | 22 | | PA | | 88-0 | 29-21-32 | D05732P | | 4 | | D05510J | | 2 | | 150-199, 275-299 |
| 005 | 22 | | PA | | 79-0 | 29-21-32 | D05732P | | 5 | | D05510J | | 3 | | 050-099 |
| 005 | 22 | | PA | | 88-0 | 29-21-32 | D05732P | | 5 | | D05510J | | 3 | | 150-199, 275-299 |
| 006 | 20 | | PA | | 5-0 | 29-21-32 | GD00852 | | D.. | 2 | D05510J | | 4 | | ALL |
| 007 | 20 | | PA | | 5-0 | 29-21-32 | GD00852 | | D.. | 2 | D05510J | | 5 | | ALL |
| 008 | 20 | | PA | | 5-0 | 29-21-32 | GD00852 | | D.. | 2 | D05510J | | 6 | | ALL |
| 009 | 24 | | PK | | 80-0 | 29-32-11 | D06244P | | A07 | \$D | D04946J | | 4 | | 050-099 |
| 009 | 24 | | PK | | 90-0 | 29-32-11 | D06244P | | A07 | \$D | D04946J | | 4 | | 150-199, 275-299 |
| 010 | 24 | | PK | | 78-0 | 29-32-11 | D06244P | | A08 | \$D | GD00852 | | D.. | 2 | 050-099 |
| 010 | 24 | | PK | | 87-0 | 29-32-11 | D06244P | | A08 | \$D | GD00852 | | D.. | 2 | 150-199, 275-299 |
| 011 | 22 | | PA | | 5-0 | 29-32-11 | GD00852 | | D.. | 2 | D04946J | | 5 | | ALL |
| 012 | 22 | | PQ | A | 67-0 | 29-33-11 | D05734J | | 17 | | D04946J | | 7 | | 050-099 |
| 012 | 22 | | PQ | A | 76-0 | 29-33-11 | D05734J | | 17 | | D04946J | | 7 | | 150-199, 275-299 |
| 012Z | | | | A | 0-0 | 29-33-11 | D05734J | | | | D04946J | FA | | FB | ALL |
| 013 | 22 | | PA | | 67-0 | 29-33-11 | D05734J | | 3 | | D04946J | | 3 | | 050-099 |
| 013 | 22 | | PA | | 76-0 | 29-33-11 | D05734J | | 3 | | D04946J | | 3 | | 150-199, 275-299 |
| 014 | 22 | | PA | | 67-0 | 29-33-11 | D05734J | | 4 | | D04946J | | 9 | | 050-099 |
| 014 | 22 | | PA | | 76-0 | 29-33-11 | D05734J | | 4 | | D04946J | | 9 | | 150-199, 275-299 |
| 015 | 22 | | PA | | 67-0 | 29-33-11 | D05734J | | 5 | | D04946J | | 10 | | 050-099 |
| 015 | 22 | | PA | | 76-0 | 29-33-11 | D05734J | | 5 | | D04946J | | 10 | | 150-199, 275-299 |
| 016 | 20 | | PA | | 5-0 | 29-33-11 | GD00852 | | S.. | 2 | D04946J | | 2 | | ALL |
| 019 | 22 | | PA | | 31-0 | 29-33-11 | D05732P | | 11 | | D05734J | | 11 | | ALL |
| 022 | 22 | | PA | | 31-0 | 29-33-11 | D05732P | | 14 | | D05734J | | 14 | | ALL |
| 023 | 22 | | PA | | 79-0 | 29-21-32 | D05510J | | 10 | | D05732P | | 6 | | 050-099 |
| 023 | 22 | | PA | | 88-0 | 29-21-32 | D05510J | | 10 | | D05732P | | 6 | | 150-199, 275-299 |
| 024 | 22 | | PA | | 79-0 | 29-21-32 | D05510J | | 1 | | D05732P | | 15 | | 050-099 |
| 024 | 22 | | PA | | 88-0 | 29-21-32 | D05510J | | 1 | | D05732P | | 15 | | 150-199, 275-299 |
| 025 | 20 | | PA | | 5-0 | 29-21-32 | D05510J | | 11 | | GD00852 | | D.. | 2 | ALL |
| 026 | 24 | | PK | | 26-0 | 29-33-11 | D06244P | | A03 | \$D | D05734J | | 12 | | ALL |
| 027 | 24 | | PK | | 26-0 | 29-33-11 | D06244P | | A06 | \$D | D05734J | | 13 | | ALL |
| 028 | 24 | | PK | | 26-0 | 29-33-11 | D06244P | | A04 | \$D | D05734J | | 9 | | ALL |
| 029 | 24 | | PK | | 26-0 | 29-33-11 | D06244P | | A05 | \$D | D05734J | | 8 | | ALL |
| 030 | 24 | | PK | | 1-0 | SPARE | D06244P | | A09 | \$D | D06244P | CAP | Y | | ALL |
| 032 | 24 | | PK | | 1-0 | SPARE | D06244P | | A10 | \$D | D06244P | CAP | Y | | ALL |
| 033 | 24 | | PK | | 1-0 | SPARE | D06244P | | A11 | \$D | D06244P | CAP | Y | | ALL |
| 201B | 24 | | PL | AA | 80-0 | 29-31-11 | D05510J | | 9 | | D06244P | A13 | \$D | | 050-099 |
| 201B | 24 | | PL | AA | 90-0 | 29-31-11 | D05510J | | 9 | | D06244P | A13 | \$D | | 150-199, 275-299 |
| 201R | 24 | | PL | AA | 0-0 | 29-31-11 | D05510J | | 8 | | D06244P | A12 | \$D | | ALL |
| 320B | 24 | | PM | AB | 13-0 | 21-64-11 | D06244P | | A14 | \$D | SP03870 | | S | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1240

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1246 | 286T1246 | | | HYDRAULICS SYSTEM, W/W (continued) | | | | | | | | | | | |
| 320R | 24 | | PM | AB | 0-0 | 21-64-11 | D06244P | A15 | \$D | | SP03872 | | S | | 050-099, 155-199, 276-299 |
| 320R | 24 | | PM | AB | 0-0 | 21-64-11 | D06244P | A19 | \$D | | SP03872 | | S | | 150-154, 275 |
| 320Y | 24 | | PM | AB | 0-0 | 21-64-11 | D06244P | A16 | \$D | | SP03874 | | S | | ALL |
| 327B | 24 | | PM | AC | 13-0 | 21-64-11 | D06244P | A17 | \$D | | SP03876 | | S | | ALL |
| 327R | 24 | | PM | AC | 0-0 | 21-64-11 | D06244P | A19 | \$D | | SP03880 | | S | | 050-099, 155-199, 276-299 |
| 327R | 24 | | PM | AC | 0-0 | 21-64-11 | D06244P | A15 | \$D | | SP03880 | | S | | 150-154, 275 |
| 327Y | 24 | | PM | AC | 0-0 | 21-64-11 | D06244P | A18 | \$D | | SP03878 | | S | | ALL |
| FRA | | | | | 0-0 | 29-33-11 | D05734J | | | FA | D05734J | | 6 | | ALL |
| FRB | | | | | 0-0 | 29-33-11 | D05734J | | | FA | D05734J | | 7 | | ALL |
| FRC | | | | | 0-0 | 29-33-11 | D05734J | | | FA | D05734J | | 18 | | ALL |
| FRD | | | | | 0-0 | 29-33-11 | D04946J | | | FB | D04946J | | 1 | | ALL |
| FRE | | | | | 0-0 | 29-33-11 | D04946J | | | FB | D04946J | | 6 | | ALL |
| FRF | | | | | 0-0 | 29-33-11 | D04946J | | | FB | D04946J | | 8 | | ALL |
| W1247 | 286T1247 | | | E1-1 & E2-1 SHELF TO P37 | | | | | | | | | | | |
| 001 | 18 | | PA | | 13-0 | 27-11-22 | D05035P | 1 | DK | | SP00225 | | 9 | | ALL |
| 002 | 22 | | PA | | 10-0 | 22-21-21 | D05035P | 2 | | | D05997P | | 2 | | ALL |
| 003 | 22 | | PA | | 10-0 | 22-21-21 | D05035P | 3 | | | D05997P | | 3 | | ALL |
| 004 | 22 | | PA | | 10-0 | 22-22-11 | D05035P | 4 | | | D05997P | | 4 | | ALL |
| 005 | 22 | | PA | | 10-0 | SPARE | D05035P | 5 | | | D05997P | | 5 | | ALL |
| 006 | 20 | | PA | | 15-0 | SPARE | D05035P | 6 | | | D05037P | | 6 | | ALL |
| 007 | 18 | | PA | | 15-0 | 27-11-22 | D05035P | 7 | DK | | D05037P | | 7 | | ALL |
| 008 | 20 | | PA | | 15-0 | 27-11-22 | D05035P | 8 | | | D05037P | | 8 | | ALL |
| 009 | 20 | | PA | | 15-0 | 27-11-22 | D05035P | 9 | | | D05037P | | 9 | | ALL |
| 010 | 18 | | PA | | 15-0 | 27-11-22 | D05035P | 10 | DK | | D05037P | | 10 | | ALL |
| 011 | 22 | | PA | | 10-0 | 27-09-14 | D05035P | 11 | | | D05997P | | 11 | | ALL |
| 012 | 20 | | PA | | 10-0 | 27-11-12 | D05035P | 12 | | | D05997P | | 12 | | ALL |
| 013 | 20 | | PA | | 10-0 | 27-11-12 | D05035P | 13 | | | D05997P | | 13 | | ALL |
| 014 | 22 | | PA | | 10-0 | 27-11-12 | D05035P | 14 | | | D05997P | | 14 | | ALL |
| 015 | 22 | | PA | | 10-0 | 27-11-12 | D05035P | 15 | | | D05997P | | 15 | | ALL |
| 016 | 22 | | PA | | 10-0 | 27-11-12 | D05035P | 16 | | | D05997P | | 16 | | ALL |
| 017 | 22 | | PA | | 10-0 | 27-11-12 | D05035P | 17 | | | D05997P | | 17 | | ALL |
| 018 | 22 | | PA | | 10-0 | 27-11-12 | D05035P | 18 | | | D05997P | | 18 | | ALL |
| 019 | 22 | | PA | | 10-0 | 27-21-12 | D05035P | 19 | | | D05997P | | 19 | | ALL |
| 020 | 22 | | PA | | 10-0 | 27-41-11 | D05035P | 20 | | | D05997P | | 20 | | ALL |
| 021 | 22 | | PA | | 10-0 | 27-41-11 | D05035P | 21 | | | D05997P | | 21 | | ALL |
| 022 | 22 | | PA | | 10-0 | 27-61-12 | D05035P | 22 | | | D05997P | | 22 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1240

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1247 | 286T1247 | | | E1-1 & E2-1 SHELF TO P37 (continued) | | | | | | | | | | | |
| 023 | 22 | | PA | | 10-0 | SPARE | D05035P | | | | 23 | | | | ALL |
| 024 | 22 | | PA | | 10-0 | SPARE | D05035P | | | | 24 | | | | ALL |
| 025 | 22 | | PA | | 10-0 | SPARE | D05035P | | | | 25 | | | | ALL |
| 028 | 22 | | PA | | 10-0 | 27-61-12 | D05035P | | | | 28 | | | | ALL |
| 029 | 22 | | PA | | 10-0 | 27-61-12 | D05035P | | | | 29 | | | | ALL |
| 030 | 22 | | PA | | 10-0 | 27-61-12 | D05035P | | | | 30 | | | | ALL |
| 031 | 22 | | PA | | 10-0 | 27-09-14 | D05035P | | | | 36 | | | | ALL |
| 032 | 22 | | PA | | 10-0 | 27-09-14 | D05035P | | | | 37 | | | | ALL |
| 033 | 22 | | PA | | 10-0 | 27-09-14 | D05035P | | | | 38 | | | | ALL |
| 034 | 22 | | PA | | 10-0 | 27-09-14 | D05035P | | | | 39 | | | | ALL |
| 035 | 22 | | PA | | 10-0 | 27-41-31 | D05997P | | | | 10 | | | | 050-099, 155-199, 275-299 |
| W1248 | 286T1248 | | | EMERGENCY EVACUATION SIGNAL SYSTEM CONTROL | | | | | | | | | | | |
| 001 | 18 | | PA | | 33-0 | 25-63-11 | D08104P | | 4 | DL | | | | | 050-099 |
| 001 | 18 | | PA | | 32-0 | 25-63-11 | D08104P | | 4 | DL | | | | | 150-199 |
| 001 | 18 | | PA | | 31-3 | 25-63-11 | D08104P | | 4 | DL | | | | | 275-299 |
| 002 | 20 | | PA | | 33-0 | 25-63-11 | D08104P | | 1 | | | | | | 050-099 |
| 002 | 20 | | PA | | 32-0 | 25-63-11 | D08104P | | 1 | | | | | | 150-199 |
| 002 | 20 | | PA | | 31-3 | 25-63-11 | D08104P | | 1 | | | | | | 275-299 |
| 003 | 20 | | PA | | 1-0 | 25-63-11 | SM00001 | | | S | | | 2 | | 050-099 |
| 003 | 20 | | PA | | 0-6 | 25-63-11 | SM00001 | | | S | | | 2 | | 150-199, 275-299 |
| 004 | 20 | | PA | | 9-0 | 25-63-11 | GD01236 | | D.. | 2 | | | 3 | | 050-099, 150-199 |
| 004 | 20 | | PA | | 8-6 | 25-63-11 | GD01236 | | D.. | 2 | | | 3 | | 275-299 |
| 005 | 20 | | PA | | 1-0 | 25-63-11 | SM00002 | | | S | | | 4 | | 050-099 |
| 005 | 20 | | PA | | 0-6 | 25-63-11 | SM00002 | | | S | | | 4 | | 150-199, 275-299 |
| 006 | 20 | | PA | | 9-0 | 25-63-11 | D02968 | | 5 | | | | S.. | 2 | 050-099 |
| 006 | 20 | | PA | | 9-0 | 25-63-11 | GD01236 | | S.. | 2 | | | 5 | | 150-199 |
| 006 | 20 | | PA | | 8-6 | 25-63-11 | GD01236 | | S.. | 2 | | | 5 | | 275-299 |
| 007 | 18 | | PA | | 24-0 | 25-63-11 | SM00001 | | | S | | | 4 | DK | 050-099 |
| 007 | 18 | | PA | | 24-0 | 25-63-11 | SM00001 | | | S | | | 4 | | 150-199 |
| 007 | 18 | | PA | | 22-3 | 25-63-11 | SM00001 | | | S | | | 4 | | 275-299 |
| 008 | 20 | | PA | | 24-0 | 25-63-11 | SM00002 | | | S | | | 1 | | 050-099, 150-199 |
| 008 | 20 | | PA | | 22-3 | 25-63-11 | SM00002 | | | S | | | 1 | | 275-299 |
| 009 | 20 | | PA | | 34-0 | 25-63-11 | SM00001 | | | S | | | 2 | | 050-099 |
| 009 | 20 | | PA | | 35-0 | 25-63-11 | SM00001 | | | S | | | 2 | | 150-199 |
| 009 | 20 | | PA | | 24-7 | 25-63-11 | SM00001 | | | S | | | 2 | | 275-299 |
| 010 | 20 | | PA | | 19-0 | 25-63-11 | GD00002 | | D.. | 2 | | | 3 | | 050-099, 150-199 |
| 010 | 20 | | PA | | 9-6 | 25-63-11 | GD00002 | | D.. | 2 | | | 3 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1240

Page 6

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|--------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1248 | 286T1248 | | | EMERGENCY EVACUATION SIGNAL SYSTEM CONTROL (continued) | | | | | | | | | | | | |
| 011 | 20 | | PA | | 34-0 | 25-63-11 | SM00002 | | | S | | | D02970 | 4 | | 050-099 |
| 011 | 20 | | PA | | 35-0 | 25-63-11 | SM00002 | | | S | | | D02970 | 4 | | 150-199 |
| 011 | 20 | | PA | | 24-6 | 25-63-11 | SM00002 | | | S | | | D02970 | 4 | | 275-299 |
| 012 | 20 | | PA | | 19-0 | 25-63-11 | GD00002 | | S.. | 2 | | | D02970 | 5 | | 050-099, 150-199 |
| 012 | 20 | | PA | | 9-6 | 25-63-11 | GD00002 | | S.. | 2 | | | D02970 | 5 | | 275-299 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1251 | 286T1251 | | | ELEC SPOILER CONT L2B,SHELF TO W/W DISC | | | | | | | | | | | |
| 001 | 20 | | PA | | 106-0 | 27-11-11 | D05167J | | | | D05702J | | | | 050-099 |
| 001 | 20 | | PA | | 116-0 | 27-11-11 | D05167J | | | | D05702J | | | | 150-199, 275-299 |
| 002 | 20 | | PA | | 106-0 | 27-11-11 | D05167J | | | | D05702J | | | | 050-099 |
| 002 | 20 | | PA | | 116-0 | 27-11-11 | D05167J | | | | D05702J | | | | 150-199, 275-299 |
| 003 | 18 | | PA | | 106-0 | SPARE | D05167J | | | | D05702J | | | | 050-099 |
| 003 | 18 | | PA | | 116-0 | SPARE | D05167J | | | | D05702J | | | | 150-199, 275-299 |
| 005 | 18 | | PA | | 124-0 | 22-21-11 | D05403P | | 17 | DK | D04559P | | 24 | DK | 050-099 |
| 005 | 18 | | PA | | 148-0 | 22-21-11 | D05403P | | 17 | DK | D04559P | | 24 | DK | 150-199, 275-299 |
| 006 | 22 | | PA | | 124-0 | 27-21-12 | D05403P | | 35 | | D04559P | | 1 | | 050-099 |
| 006 | 22 | | PA | | 148-0 | 27-21-12 | D05403P | | 35 | | D04559P | | 1 | | 150-199, 275-299 |
| 007Y | 22 | | PJ | | 124-0 | 27-41-11 | D05403P | | 25 | | D04477P | | 8 | | 050-099 |
| 007Y | 22 | | PJ | | 147-0 | 27-41-11 | D05403P | | 25 | | D04477P | | 8 | | 150-199, 275-299 |
| 008Y | 22 | | PJ | | 124-0 | 27-41-11 | D05403P | | 26 | | D04477P | | 9 | | 050-099 |
| 008Y | 22 | | PJ | | 147-0 | 27-41-11 | D05403P | | 26 | | D04477P | | 9 | | 150-199, 275-299 |
| 009 | 22 | | PA | | 124-0 | 27-41-11 | D05403P | | 27 | | D04477P | | 1 | | 050-099 |
| 009 | 22 | | PA | | 147-0 | 27-41-11 | D05403P | | 27 | | D04477P | | 1 | | 150-199, 275-299 |
| 010 | 22 | | PA | | 124-0 | SPARE | D05403P | | 40 | | D04559P | | 13 | | 050-099 |
| 010 | 22 | | PA | | 148-0 | SPARE | D05403P | | 40 | | D04559P | | 13 | | 150-199, 275-299 |
| 011 | 22 | | PA | | 124-0 | SPARE | D05403P | | 41 | | D04477P | | 10 | | 050-099 |
| 011 | 22 | | PA | | 147-0 | SPARE | D05403P | | 41 | | D04477P | | 10 | | 150-199, 275-299 |
| 201B | 20 | | PB | IA | 104-0 | 27-61-16 | D05403P | | 3 | | D05211P | | 3 | | 050-099 |
| 201B | 20 | | PB | IA | 114-0 | 27-61-16 | D05403P | | 3 | | D05211P | | 3 | | 150-199, 275-299 |
| 201R | 20 | | PB | IA | 0-0 | 27-61-16 | D05403P | | 1 | | D05211P | | 1 | | ALL |
| 203B | 20 | | PB | IC | 104-0 | 27-61-16 | D05403P | | 9 | | D05211P | | 4 | | 050-099 |
| 203B | 20 | | PB | IC | 114-0 | 27-61-16 | D05403P | | 9 | | D05211P | | 4 | | 150-199, 275-299 |
| 203R | 20 | | PB | IC | 0-0 | 27-61-16 | D05403P | | 8 | | D05211P | | 2 | | ALL |
| 204B | 20 | | PB | ID | 111-0 | 27-61-16 | D05403P | | 11 | | D05221P | | 3 | | 050-099 |
| 204B | 20 | | PB | ID | 121-0 | 27-61-16 | D05403P | | 11 | | D05221P | | 3 | | 150-199, 275-299 |
| 204R | 20 | | PB | ID | 0-0 | 27-61-16 | D05403P | | 10 | | D05221P | | 1 | | ALL |
| 206B | 20 | | PB | IF | 111-0 | 27-61-16 | D05403P | | 15 | | D05221P | | 4 | | 050-099 |
| 206B | 20 | | PB | IF | 121-0 | 27-61-16 | D05403P | | 15 | | D05221P | | 4 | | 150-199, 275-299 |
| 206R | 20 | | PB | IF | 0-0 | 27-61-16 | D05403P | | 14 | | D05221P | | 2 | | ALL |
| 207B | 22 | | PB | IG | 124-0 | 22-21-11 | D05403P | | 19 | | D04559P | | 20 | | 050-099 |
| 207B | 22 | | PB | IG | 148-0 | 22-21-11 | D05403P | | 19 | | D04559P | | 20 | | 150-199, 275-299 |
| 207R | 22 | | PB | IG | 0-0 | 22-21-11 | D05403P | | 18 | | D04559P | | 19 | | ALL |
| 208B | 22 | | PB | IH | 124-0 | 22-21-11 | D05403P | | 24 | | D04559P | | 22 | | 050-099 |
| 208B | 22 | | PB | IH | 148-0 | 22-21-11 | D05403P | | 24 | | D04559P | | 22 | | 150-199, 275-299 |
| 208R | 22 | | PB | IH | 0-0 | 22-21-11 | D05403P | | 23 | | D04559P | | 21 | | ALL |
| 209B | 22 | | PB | II | 124-0 | 27-21-12 | D05403P | | 29 | | D04559P | | 7 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 1

Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | |
|--------------|-----------------|----|-------|--|----------|---------|---------|-------|------|------|---------|-------|-------------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term |
| W1251 | 286T1251 | | | ELEC SPOILER CONT L2B,SHELF TO W/W DISC (continued) | | | | | | | | | | |
| 209B | 22 | PB | II | 148-0 | 27-21-12 | D05403P | | 29 | | | D04559P | 7 | | 150-199, 275-299 |
| 209R | 22 | PB | II | 0-0 | 27-21-12 | D05403P | | 28 | | | D04559P | 6 | | ALL |
| 210B | 22 | PB | IJ | 124-0 | 27-21-12 | D05403P | | 34 | | | D04559P | 10 | | 050-099 |
| 210B | 22 | PB | IJ | 148-0 | 27-21-12 | D05403P | | 34 | | | D04559P | 10 | | 150-199, 275-299 |
| 210R | 22 | PB | IJ | 0-0 | 27-21-12 | D05403P | | 33 | | | D04559P | 9 | | ALL |
| 301B | 20 | PC | MA | 104-0 | 27-61-16 | D05403P | | 4 | | | D05211P | 6 | | 050-099 |
| 301B | 20 | PC | MA | 114-0 | 27-61-16 | D05403P | | 4 | | | D05211P | 6 | | 150-199, 275-299 |
| 301R | 20 | PC | MA | 0-0 | 27-61-16 | D05403P | | 5 | | | D05211P | 5 | | ALL |
| 301Y | 20 | PC | MA | 0-0 | 27-61-16 | D05403P | | 7 | | | D05211P | 7 | | ALL |
| 302B | 20 | PC | MB | 111-0 | 27-61-16 | D05403P | | 6 | | | D05221P | 6 | | 050-099 |
| 302B | 20 | PC | MB | 121-0 | 27-61-16 | D05403P | | 6 | | | D05221P | 6 | | 150-199, 275-299 |
| 302R | 20 | PC | MB | 0-0 | 27-61-16 | D05403P | | 12 | | | D05221P | 5 | | ALL |
| 302Y | 20 | PC | MB | 0-0 | 27-61-16 | D05403P | | 13 | | | D05221P | 7 | | ALL |
| 303B | 22 | PC | MC | 124-0 | 22-21-11 | D05403P | | 21 | | | D04559P | 17 | | 050-099 |
| 303B | 22 | PC | MC | 148-0 | 22-21-11 | D05403P | | 21 | | | D04559P | 17 | | 150-199, 275-299 |
| 303R | 22 | PC | MC | 0-0 | 22-21-11 | D05403P | | 20 | | | D04559P | 16 | | ALL |
| 303Y | 22 | PC | MC | 0-0 | 22-21-11 | D05403P | | 22 | | | D04559P | 18 | | ALL |
| 304B | 22 | PC | MD | 124-0 | 27-21-12 | D05403P | | 31 | | | D04559P | 3 | | 050-099 |
| 304B | 22 | PC | MD | 148-0 | 27-21-12 | D05403P | | 31 | | | D04559P | 3 | | 150-199, 275-299 |
| 304R | 22 | PC | MD | 0-0 | 27-21-12 | D05403P | | 30 | | | D04559P | 2 | | ALL |
| 304Y | 22 | PC | MD | 0-0 | 27-21-12 | D05403P | | 32 | | | D04559P | 4 | | ALL |
| W1252 | 286T1252 | | | EMERGENCY EVACUATION SIGNAL SYSTEM CONTROL,MID | | | | | | | | | | |
| 001 | 18 | PA | | 52-0 | 25-63-11 | D08098P | | 4 | | | SM00001 | | S | 050-099 |
| 001 | 18 | PA | | 66-0 | 25-63-11 | D08098P | | 4 | | | SM00001 | | S | 150-199 |
| 001 | 18 | PA | | 55-0 | 25-63-11 | D08098P | | 4 | | | SM00001 | | S | 275-299 |
| 002 | 20 | PA | | 52-0 | 25-63-11 | D08098P | | 1 | | | SM00002 | | S | 050-099 |
| 002 | 20 | PA | | 66-0 | 25-63-11 | D08098P | | 1 | | | SM00002 | | S | 150-199 |
| 002 | 20 | PA | | 55-0 | 25-63-11 | D08098P | | 1 | | | SM00002 | | S | 275-299 |
| 003 | 20 | PA | | 1-0 | 25-63-11 | SM00001 | | | S | | D06026J | 2 | | 050-099 |
| 003 | 20 | PA | | 17-0 | 25-63-11 | SM00001 | | | S | | D06026J | 2 | | 150-199 |
| 003 | 20 | PA | | 2-0 | 25-63-11 | SM00001 | | | S | | D06026J | 2 | | 275-299 |
| 004 | 20 | PA | | 5-0 | 25-63-11 | GD00934 | | D.. | 2 | | D06026J | 3 | | 050-099 |
| 004 | 20 | PA | | 5-0 | 25-63-11 | GD01950 | | D.. | 2 | | D06026J | 3 | | 150-199 |
| 004 | 20 | PA | | 5-0 | 25-63-11 | GD04198 | | D.. | 2 | | D06026J | 3 | | 275-299 |
| 005 | 20 | PA | | 1-0 | 25-63-11 | SM00002 | | | S | | D06026J | 4 | | 050-099 |
| 005 | 20 | PA | | 17-0 | 25-63-11 | SM00002 | | | S | | D06026J | 4 | | 150-199 |
| 005 | 20 | PA | | 2-0 | 25-63-11 | SM00002 | | | S | | D06026J | 4 | | 275-299 |
| 006 | 20 | PA | | 5-0 | 25-63-11 | GD00934 | | S.. | 2 | | D06026J | 5 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|---------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1252 | 286T1252 | | | EMERGENCY EVACUATION SIGNAL SYSTEM CONTROL,MID (continued) | | | | | | | | | | | |
| 006 | 20 | | PA | | 5-0 | 25-63-11 | GD01950 | S.. | 2 | | D06026J | | 5 | | 150-199 |
| 006 | 20 | | PA | | 5-0 | 25-63-11 | GD04198 | S.. | 2 | | D06026J | | 5 | | 275-299 |
| 007 | 18 | | PA | | 26-0 | 25-63-11 | SM00001 | | | S | D08100P | | 4 | DK | 050-099 |
| 007 | 18 | | PA | | 2-0 | 25-63-11 | SM00001 | | | S | D08100P | | 4 | DK | 150-199 |
| 007 | 18 | | PA | | 30-0 | 25-63-11 | SM00001 | | | S | D08100P | | 4 | DK | 275-299 |
| 008 | 20 | | PA | | 26-0 | 25-63-11 | SM00002 | | | S | D08100P | | 1 | | 050-099 |
| 008 | 20 | | PA | | 2-0 | 25-63-11 | SM00002 | | | S | D08100P | | 1 | | 150-199 |
| 008 | 20 | | PA | | 30-0 | 25-63-11 | SM00002 | | | S | D08100P | | 1 | | 275-299 |
| W1253 | 286T1253 | | | ELEC SPOILER CONT L2C,SHELF TO W/W DISC | | | | | | | | | | | |
| 201B | 20 | | PB | IA | 99-0 | 27-61-15 | D05405P | | | 3 | D05213P | | 3 | | 050-099 |
| 201B | 20 | | PB | IA | 111-0 | 27-61-15 | D05405P | | | 3 | D05213P | | 3 | | 150-199, 275-299 |
| 201R | 20 | | PB | IA | 0-0 | 27-61-15 | D05405P | | | 1 | D05213P | | 1 | | ALL |
| 203B | 20 | | PB | IC | 99-0 | 27-61-15 | D05405P | | | 9 | D05213P | | 4 | | 050-099 |
| 203B | 20 | | PB | IC | 111-0 | 27-61-15 | D05405P | | | 9 | D05213P | | 4 | | 150-199, 275-299 |
| 203R | 20 | | PB | IC | 0-0 | 27-61-15 | D05405P | | | 8 | D05213P | | 2 | | ALL |
| 204B | 20 | | PB | ID | 107-0 | 27-61-15 | D05405P | | | 11 | D05219P | | 3 | | 050-099 |
| 204B | 20 | | PB | ID | 118-0 | 27-61-15 | D05405P | | | 11 | D05219P | | 3 | | 150-199, 275-299 |
| 204R | 20 | | PB | ID | 0-0 | 27-61-15 | D05405P | | | 10 | D05219P | | 1 | | ALL |
| 206B | 20 | | PB | IF | 107-0 | 27-61-15 | D05405P | | | 15 | D05219P | | 4 | | 050-099 |
| 206B | 20 | | PB | IF | 118-0 | 27-61-15 | D05405P | | | 15 | D05219P | | 4 | | 150-199, 275-299 |
| 206R | 20 | | PB | IF | 0-0 | 27-61-15 | D05405P | | | 14 | D05219P | | 2 | | ALL |
| 302B | 20 | | PC | MB | 99-0 | 27-61-15 | D05405P | | | 6 | D05213P | | 6 | | 050-099 |
| 302B | 20 | | PC | MB | 111-0 | 27-61-15 | D05405P | | | 6 | D05213P | | 6 | | 150-199, 275-299 |
| 302R | 20 | | PC | MB | 0-0 | 27-61-15 | D05405P | | | 5 | D05213P | | 5 | | ALL |
| 302Y | 20 | | PC | MB | 0-0 | 27-61-15 | D05405P | | | 7 | D05213P | | 7 | | ALL |
| 303B | 20 | | PC | MC | 107-0 | 27-61-15 | D05405P | | | 16 | D05219P | | 6 | | 050-099 |
| 303B | 20 | | PC | MC | 118-0 | 27-61-15 | D05405P | | | 16 | D05219P | | 6 | | 150-199, 275-299 |
| 303R | 20 | | PC | MC | 0-0 | 27-61-15 | D05405P | | | 12 | D05219P | | 5 | | ALL |
| 303Y | 20 | | PC | MC | 0-0 | 27-61-15 | D05405P | | | 13 | D05219P | | 7 | | ALL |
| W1254 | 286T1254 | | | EMERGENCY EVACUATION SIGNAL CONTROL | | | | | | | | | | | |
| 001 | 18 | | PA | | 55-0 | 25-63-11 | D08102P | | | 4 | DL | SM00001 | | S | 050-099 |
| 001 | 18 | | PA | | 66-0 | 25-63-11 | D08102P | | | 4 | DL | SM00001 | | S | 150-199, 275-299 |
| 002 | 20 | | PA | | 55-0 | 25-63-11 | D08102P | | | 1 | | SM00002 | | S | 050-099 |
| 002 | 20 | | PA | | 66-0 | 25-63-11 | D08102P | | | 1 | | SM00002 | | S | 150-199, 275-299 |
| 003 | 20 | | PA | | 24-0 | 25-63-11 | SM00001 | | | | S | D02974 | | 2 | ALL |
| 004 | 20 | | PA | | 27-0 | 25-63-11 | GD00070 | | | D.. | 2 | D02974 | | 3 | 050-099 |
| 004 | 20 | | PA | | 23-0 | 25-63-11 | GD00070 | | | D.. | 2 | D02974 | | 3 | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 3

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1254 | 286T1254 | | | EMERGENCY EVACUATION SIGNAL CONTROL (continued) | | | | | | | | | | | | |
| 004 | 20 | | PA | 13-0 | 25-63-11 | GD00054 | D.. | 2 | | D02974 | | 3 | | 275-299 | | |
| 005 | 20 | | PA | 24-0 | 25-63-11 | SM00002 | | S | | D02974 | | 4 | | ALL | | |
| 006 | 20 | | PA | 27-0 | 25-63-11 | GD00070 | S.. | 2 | | D02974 | | 5 | | 050-099 | | |
| 006 | 20 | | PA | 23-0 | 25-63-11 | GD00070 | S.. | 2 | | D02974 | | 5 | | 150-199 | | |
| 006 | 20 | | PA | 13-0 | 25-63-11 | GD00054 | S.. | 2 | | D02974 | | 5 | | 275-299 | | |
| 007 | 20 | | PA | 25-0 | 25-63-11 | SM00001 | | S | | D02976 | | 2 | | ALL | | |
| 008 | 20 | | PA | 21-0 | 25-63-11 | GD00932 | D.. | 2 | | D02976 | | 3 | | 050-099 | | |
| 008 | 20 | | PA | 23-0 | 25-63-11 | GD00932 | D.. | 2 | | D02976 | | 3 | | 150-199 | | |
| 008 | 20 | | PA | 12-0 | 25-63-11 | GD04506 | D.. | 2 | | D02976 | | 3 | | 275-299 | | |
| 009 | 20 | | PA | 25-0 | 25-63-11 | SM00002 | | S | | D02976 | | 4 | | ALL | | |
| 010 | 20 | | PA | 21-0 | 25-63-11 | GD00932 | S.. | 2 | | D02976 | | 5 | | 050-099 | | |
| 010 | 20 | | PA | 23-0 | 25-63-11 | GD00932 | S.. | 2 | | D02976 | | 5 | | 150-199 | | |
| 010 | 20 | | PA | 12-0 | 25-63-11 | GD04506 | S.. | 2 | | D02976 | | 5 | | 275-299 | | |
| W1255 | 286T1255 | | | ELECT SPOILER CONT L2A,SHELF TO W/W DISC | | | | | | | | | | | | |
| 201B | 20 | | PB IA | 83-0 | 27-61-14 | D05411P | | 3 | | D05215P | | 3 | | 050-099 | | |
| 201B | 20 | | PB IA | 93-0 | 27-61-14 | D05411P | | 3 | | D05215P | | 3 | | 150-199, 275-299 | | |
| 201R | 20 | | PB IA | 0-0 | 27-61-14 | D05411P | | 1 | | D05215P | | 1 | | ALL | | |
| 203B | 20 | | PB IC | 83-0 | 27-61-14 | D05411P | | 9 | | D05215P | | 4 | | 050-099 | | |
| 203B | 20 | | PB IC | 93-0 | 27-61-14 | D05411P | | 9 | | D05215P | | 4 | | 150-199, 275-299 | | |
| 203R | 20 | | PB IC | 0-0 | 27-61-14 | D05411P | | 8 | | D05215P | | 2 | | ALL | | |
| 204B | 20 | | PB ID | 93-0 | 27-61-14 | D05411P | | 11 | | D05217P | | 3 | | 050-099 | | |
| 204B | 20 | | PB ID | 102-0 | 27-61-14 | D05411P | | 11 | | D05217P | | 3 | | 150-199, 275-299 | | |
| 204R | 20 | | PB ID | 0-0 | 27-61-14 | D05411P | | 10 | | D05217P | | 1 | | ALL | | |
| 206B | 20 | | PB IF | 93-0 | 27-61-14 | D05411P | | 15 | | D05217P | | 4 | | 050-099 | | |
| 206B | 20 | | PB IF | 102-0 | 27-61-14 | D05411P | | 15 | | D05217P | | 4 | | 150-199, 275-299 | | |
| 206R | 20 | | PB IF | 0-0 | 27-61-14 | D05411P | | 14 | | D05217P | | 2 | | ALL | | |
| 301B | 20 | | PC MA | 83-0 | 27-61-14 | D05411P | | 4 | | D05215P | | 6 | | 050-099 | | |
| 301B | 20 | | PC MA | 93-0 | 27-61-14 | D05411P | | 4 | | D05215P | | 6 | | 150-199, 275-299 | | |
| 301R | 20 | | PC MA | 0-0 | 27-61-14 | D05411P | | 5 | | D05215P | | 5 | | ALL | | |
| 301Y | 20 | | PC MA | 0-0 | 27-61-14 | D05411P | | 7 | | D05215P | | 7 | | ALL | | |
| 302B | 20 | | PC MB | 93-0 | 27-61-14 | D05411P | | 6 | | D05217P | | 6 | | 050-099 | | |
| 302B | 20 | | PC MB | 102-0 | 27-61-14 | D05411P | | 6 | | D05217P | | 6 | | 150-199, 275-299 | | |
| 302R | 20 | | PC MB | 0-0 | 27-61-14 | D05411P | | 12 | | D05217P | | 5 | | ALL | | |
| 302Y | 20 | | PC MB | 0-0 | 27-61-14 | D05411P | | 13 | | D05217P | | 7 | | ALL | | |
| W1256 | 286T1256 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS | | | | | | | | | | | | |
| 001 | 20 | | PA | 113-7 | 30-71-23 | D05820P | | 7 | | D06304P | | 2 | | 050-099 | | |
| 001 | 22 | | PA | 134-9 | 30-71-23 | D05820P | | 7 | | D06304P | | 2 | | 150-154, 275 | | |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1256 | 286T1256 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | | | |
| 001 | 20 | | PA | 134-10 | 30-71-23 | D05820P | | 7 | | | | | D06304P | 2 | | | 155-199 |
| 001 | 22 | | PA | 134-10 | 30-71-23 | D05820P | | 7 | | | | | D06304P | 2 | | | 276-299 |
| 002 | 20 | | PA | 103-11 | 30-71-24 | D05688P | | 18 | | | | | D06304P | 6 | | | 050-099 |
| 002 | 22 | | PA | 134-9 | 30-71-23 | D05820P | | 2 | | | | | D06304P | 6 | | | 150-154, 275 |
| 002 | 20 | | PA | 134-10 | 30-71-23 | D05820P | | 2 | | | | | D06304P | 6 | | | 155-199 |
| 002 | 22 | | PA | 134-10 | 30-71-23 | D05820P | | 2 | | | | | D06304P | 6 | | | 276-299 |
| 003 | 20 | | PA | 103-11 | 30-71-24 | D05688P | | 16 | | | | | D06304P | 4 | | | 050-099 |
| 003 | 22 | | PA | 134-9 | 30-71-23 | D05820P | | 3 | | | | | D06304P | 4 | | | 150-154, 275 |
| 003 | 20 | | PA | 134-10 | 30-71-23 | D05820P | | 3 | | | | | D06304P | 4 | | | 155-199 |
| 003 | 22 | | PA | 134-10 | 30-71-23 | D05820P | | 3 | | | | | D06304P | 4 | | | 276-299 |
| 010 | 20 | | PA | 103-11 | 30-71-24 | D05688P | | 3 | | | | | D06304P | 1 | | | 050-099 |
| 010 | 20 | | PA | 134-9 | 30-71-23 | D05820P | | 6 | | | | | D06304P | 1 | | | 150-154 |
| 010 | 20 | | PA | 134-10 | 30-71-23 | D05820P | | 6 | | | | | D06304P | 1 | | | 155-199 |
| 010 | 22 | | PA | 152-10 | 30-71-23 | D05820P | | 6 | | | | | D06302P | 1 | | | 275 |
| 010 | 22 | | PA | 152-2 | 30-71-23 | D05820P | | 6 | | | | | D06302P | 1 | | | 276-299 |
| 011 | 20 | | PA | 113-7 | 30-71-23 | D05820P | | 4 | | | | | D06304P | 5 | | | 050-099 |
| 011 | 20 | | PA | 124-11 | 30-71-24 | D05688P | | 3 | | | | | D06304P | 5 | | | 150-199 |
| 017 | 18 | | PA | 13-1 | 30-71-11 | D05820P | | 9 | DL | | | | D05688P | 9 | DL | | 050-099, 150-154, 275 |
| 017 | 18 | | PA | 13-3 | 30-71-11 | D05820P | | 9 | DL | | | | D05688P | 9 | DL | | 155-199, 276-299 |
| 018 | 20 | | PA | 13-1 | 30-71-11 | D05820P | | 10 | | | | | D05688P | 10 | | | 050-099, 150-154, 275 |
| 018 | 20 | | PA | 13-3 | 30-71-11 | D05820P | | 10 | | | | | D05688P | 10 | | | 155-199, 276-299 |
| 020 | 18 | | PA | 122-1 | 30-71-11 | D05688P | | 1 | DL | | | | D06302P | 4 | DK | | 050-099 |
| 020 | 18 | | PA | 143-1 | 30-71-11 | D05688P | | 1 | DL | | | | D06302P | 4 | DK | | 150-154, 275 |
| 020 | 18 | | PA | 142-2 | 30-71-11 | D05688P | | 1 | DL | | | | D06302P | 4 | DK | | 155-199, 276-299 |
| 022 | 24 | | PK | 104-1 | 36-11-41 | D05688P | | 5 | | | | | D05874J | 5 | | | 050-099 |
| 022 | 24 | | PK | 125-6 | 36-11-41 | D05688P | | 5 | | | | | D05874J | 5 | | | 150-154, 275 |
| 022 | 24 | | PK | 125-5 | 36-11-41 | D05688P | | 5 | | | | | D05874J | 5 | | | 155-199, 276-299 |
| 023 | 24 | | PK | 125-6 | 36-11-41 | D05688P | | 6 | | | | | D05874J | 6 | | | 150-154 |
| 023 | 24 | | PK | 125-5 | 36-11-41 | D05688P | | 6 | | | | | D05874J | 6 | | | 155-157 |
| 024 | 22 | | PA | 104-1 | 36-11-41 | D05688P | | 7 | | | | | D05874J | 7 | | | 050-099 |
| 024 | 22 | | PA | 125-6 | 36-11-41 | D05688P | | 7 | | | | | D05874J | 7 | | | 150-154, 275 |
| 024 | 22 | | PA | 125-5 | 36-11-41 | D05688P | | 7 | | | | | D05874J | 7 | | | 155-199, 276-299 |
| 025 | 24 | | PK | 104-1 | 36-11-41 | D05688P | | 8 | | | | | D05874J | 8 | | | 050-099 |
| 025 | 24 | | PK | 125-6 | 36-11-41 | D05688P | | 8 | | | | | D05874J | 8 | | | 150-154, 275 |
| 025 | 24 | | PK | 125-5 | 36-11-41 | D05688P | | 8 | | | | | D05874J | 8 | | | 155-199, 276-299 |
| 028 | 24 | | PK | 103-11 | 21-44-21 | D05688P | | 13 | | | | | D06304P | 19 | | | 050-099 |
| 028 | 24 | | PK | 124-11 | 21-44-21 | D05688P | | 13 | | | | | D06304P | 8 | | | 150-199 |
| 028 | 24 | | PK | 124-11 | 21-44-21 | D05688P | | 13 | | | | | D06304P | 19 | | | 275-299 |
| 029 | 24 | | PK | 103-11 | 21-44-21 | D05688P | | 14 | | | | | D06304P | 20 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1256 | 286T1256 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | | | |
| 029 | 24 | | PK | 124-11 | 21-44-21 | D05688P | | 14 | | | | | D06304P | 9 | | | 150-199 |
| 029 | 24 | | PK | 124-11 | 21-44-21 | D05688P | | 14 | | | | | D06304P | 20 | | | 275-299 |
| 032 | 24 | | PK | 21-1 | 38-15-11 | D05874J | | 1 | | | | | SP01466 | | S | | 050-099 |
| 032 | 24 | | PK | 21-9 | 38-15-11 | D05874J | | 1 | | | | | SP01466 | | S | | 150-154, 275 |
| 032 | 24 | | PK | 21-6 | 38-15-11 | D05874J | | 1 | | | | | SP01466 | | S | | 155-199, 276-299 |
| 033 | 24 | | PK | 3-7 | 38-15-11 | D05874J | | 2 | | | | | D06304P | 18 | | | 050-099 |
| 033 | 24 | | PK | 3-2 | 38-15-11 | D05874J | | 2 | | | | | D06304P | 7 | | | 150-154 |
| 033 | 24 | | PK | 4-4 | 38-15-11 | D05874J | | 2 | | | | | D06304P | 7 | | | 155-199 |
| 033 | 24 | | PK | 3-2 | 38-15-11 | D05874J | | 2 | | | | | D06304P | 18 | | | 275 |
| 033 | 24 | | PK | 4-4 | 38-15-11 | D05874J | | 2 | | | | | D06304P | 18 | | | 276-299 |
| 034 | 24 | | PK | 104-1 | 38-15-11 | D05874J | | 3 | | | | | D05688P | 15 | | | 050-099 |
| 034 | 24 | | PK | 125-6 | 38-15-11 | D05874J | | 3 | | | | | D05688P | 15 | | | 150-154, 275 |
| 034 | 24 | | PK | 125-5 | 38-15-11 | D05874J | | 3 | | | | | D05688P | 15 | | | 155-199, 276-299 |
| 036 | 20 | | PA | 131-10 | 30-71-23 | D05820P | | 1 | | | | | D06302P | 2 | | | 050-099 |
| 036 | 22 | | PA | 152-10 | 30-71-23 | D05820P | | 1 | | | | | D06302P | 2 | | | 150-154, 275 |
| 036 | 20 | | PA | 152-2 | 30-71-23 | D05820P | | 1 | | | | | D06302P | 2 | | | 155-199 |
| 036 | 22 | | PA | 152-2 | 30-71-23 | D05820P | | 1 | | | | | D06302P | 2 | | | 276-299 |
| 042 | 20 | | PA | 103-11 | 30-71-24 | D05688P | | 17 | | | | | D06304P | 3 | | | 050-099 |
| 042 | 20 | | PA | 134-9 | 30-71-23 | D05820P | | 5 | | | | | D06304P | 3 | | | 150-154 |
| 042 | 20 | | PA | 134-10 | 30-71-23 | D05820P | | 5 | | | | | D06304P | 3 | | | 155-199 |
| 042 | 20 | | PA | 152-10 | 30-71-23 | D05820P | | 5 | | | | | D06302P | 3 | | | 275 |
| 042 | 20 | | PA | 152-2 | 30-71-23 | D05820P | | 5 | | | | | D06302P | 3 | | | 276 |
| 042 | 22 | | PA | 134-10 | 30-71-23 | D05820P | | 5 | | | | | D06304P | 3 | | | 277-299 |
| 047 | 18 | | PA | 113-9 | 38-15-11 | D05820P | | 20 | DL | | | | D05874J | 13 | DK | | 050-099 |
| 047 | 18 | | PA | 135-4 | 38-15-11 | D05820P | | 20 | DL | | | | D05874J | 13 | DK | | 150-154, 275 |
| 047 | 18 | | PA | 135-5 | 38-15-11 | D05820P | | 20 | DL | | | | D05874J | 13 | DK | | 155-199, 276-299 |
| 048 | 18 | | PA | 113-9 | 38-15-11 | D05820P | | 21 | DL | | | | D05874J | 14 | DK | | 050-099 |
| 048 | 18 | | PA | 135-4 | 38-15-11 | D05820P | | 21 | DL | | | | D05874J | 14 | DK | | 150-154, 275 |
| 048 | 18 | | PA | 135-5 | 38-15-11 | D05820P | | 21 | DL | | | | D05874J | 14 | DK | | 155-199, 276-299 |
| 049 | 18 | | PA | 113-9 | 38-15-11 | D05820P | | 22 | DL | | | | D05874J | 15 | DK | | 050-099 |
| 049 | 18 | | PA | 135-4 | 38-15-11 | D05820P | | 22 | DL | | | | D05874J | 15 | DK | | 150-154, 275 |
| 049 | 18 | | PA | 135-5 | 38-15-11 | D05820P | | 22 | DL | | | | D05874J | 15 | DK | | 155-199, 276-299 |
| 051 | 18 | | PA | 104-1 | 38-32-11 | D05688P | | 11 | DL | | | | D05874J | 4 | DK | | 050-099 |
| 051 | 18 | | PA | 125-6 | 38-32-11 | D05688P | | 11 | DL | | | | D05874J | 4 | DK | | 150-154, 275 |
| 051 | 18 | | PA | 125-5 | 38-32-11 | D05688P | | 11 | DL | | | | D05874J | 4 | DK | | 155-199, 276-299 |
| 071 | 20 | | PA | 113-7 | 30-71-23 | D05820P | | 13 | | | | | D06304P | 10 | | | 050-099 |
| 071 | 22 | | PA | 134-9 | 30-71-23 | D05820P | | 13 | | | | | D06304P | 10 | | | 150-154 |
| 071 | 20 | | PA | 134-10 | 30-71-23 | D05820P | | 13 | | | | | D06304P | 10 | | | 155-199 |
| 071 | 22 | | PA | 134-9 | 30-71-23 | D05820P | | 13 | | | | | D06304P | 22 | | | 275 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|--------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1256 | 286T1256 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | |
| 071 | 22 | | PA | | 134-10 | 30-71-23 | D05820P | | | | 13 | | | | 276-299 |
| 072 | 20 | | PA | | 113-7 | 30-71-23 | D05820P | | | | 14 | | | | 050-099 |
| 072 | 22 | | PA | | 134-9 | 30-71-23 | D05820P | | | | 14 | | | | 150-154 |
| 072 | 20 | | PA | | 134-10 | 30-71-23 | D05820P | | | | 14 | | | | 155-199 |
| 072 | 22 | | PA | | 134-9 | 30-71-23 | D05820P | | | | 14 | | | | 275 |
| 072 | 22 | | PA | | 134-10 | 30-71-23 | D05820P | | | | 14 | | | | 276-299 |
| 075 | 20 | | PA | | 131-10 | 30-71-23 | D05820P | | | | 15 | | | | 050-099 |
| 075 | 22 | | PA | | 152-10 | 30-71-23 | D05820P | | | | 15 | | | | 150-154, 275 |
| 075 | 20 | | PA | | 152-2 | 30-71-23 | D05820P | | | | 15 | | | | 155-199 |
| 075 | 22 | | PA | | 152-2 | 30-71-23 | D05820P | | | | 15 | | | | 276-299 |
| 079 | 18 | | PA | | 104-1 | 38-32-14 | D05688P | | | | 24 | DL | | | 050-099 |
| 079 | 18 | | PA | | 125-6 | 38-32-14 | D05688P | | | | 24 | DL | | | 150-154, 275 |
| 079 | 18 | | PA | | 125-5 | 38-32-14 | D05688P | | | | 24 | DL | | | 155-199, 276-299 |
| 096 | 22 | | PA | | 25-5 | 21-45-22 | D06810J | | | | 1 | | | | 050-099 |
| 096 | 22 | | PA | | 35-0 | 21-45-22 | D06810J | | | | 1 | | | | 150-154, 275 |
| 096 | 22 | | PA | | 24-5 | 21-45-22 | D06810J | | | | 1 | | | | 155-199, 276-299 |
| 097 | 20 | | PA | | 11-0 | 21-45-22 | D06810J | | | | 2 | | A.. | E | 050-099 |
| 097 | 20 | | PA | | 10-0 | 21-45-22 | D06810J | | | | 2 | | A.. | E | 150-154, 275 |
| 097 | 20 | | PA | | 7-7 | 21-45-22 | D06810J | | | | 2 | | A.. | E | 155-199, 276-299 |
| 098 | 18 | | PA | | 3-6 | 21-45-22 | D06810J | | | | 3 | DK | S.. | E | 050-099 |
| 098 | 18 | | PA | | 5-0 | 21-45-22 | D06810J | | | | 3 | DK | S.. | E | 150-154, 275 |
| 098 | 18 | | PA | | 4-1 | 21-45-22 | D06810J | | | | 3 | DK | S.. | E | 155-199, 276-299 |
| 101 | 22 | | PA | | 65-7 | 21-45-22 | D05688P | | | | 12 | | | | 050-099 |
| 101 | 22 | | PA | | 115-0 | 21-45-22 | D05688P | | | | 12 | | | | 150-154, 275 |
| 101 | 22 | | PA | | 79-10 | 21-45-22 | D05688P | | | | 12 | | | | 155-199, 276-299 |
| 104 | 22 | | PA | | 29-0 | 21-45-22 | D06812J | | | | 1 | | | | 150-154, 275 |
| 104 | 22 | | PA | | 23-5 | 21-45-22 | D06812J | | | | 1 | | | | 155-199, 276-299 |
| 105 | 20 | | PA | | 17-0 | 21-45-22 | D06812J | | | | 2 | | A.. | E | 150-154 |
| 105 | 20 | | PA | | 17-2 | 21-45-22 | D06812J | | | | 2 | | A.. | E | 155-199, 276-299 |
| 105 | 20 | | PA | | 25-0 | 21-45-22 | D06812J | | | | 2 | | A.. | E | 275 |
| 106 | 18 | | PA | | 8-0 | 21-45-22 | D06812J | | | | 3 | DK | S.. | E | 150-154 |
| 106 | 18 | | PA | | 4-7 | 21-45-22 | D06812J | | | | 3 | DK | S.. | E | 155-199, 276-299 |
| 106 | 18 | | PA | | 12-0 | 21-45-22 | D06812J | | | | 3 | DK | S.. | E | 275 |
| 107 | 22 | | PA | | 10-1 | 21-45-22 | D06814J | | | | 1 | | | | 050-099 |
| 107 | 22 | | PA | | 115-0 | 21-45-22 | D06814J | | | | 1 | | | | 150-154 |
| 107 | 22 | | PA | | 8-10 | 21-45-22 | D06814J | | | | 1 | | | | 155-199, 276-299 |
| 107 | 22 | | PA | | 25-0 | 21-45-22 | D06814J | | | | 1 | | | | 275 |
| 108 | 20 | | PA | | 7-11 | 21-45-22 | D06814J | | | | 2 | | A.. | E | 050-099 |
| 108 | 20 | | PA | | 10-0 | 21-45-22 | D06814J | | | | 2 | | A.. | E | 150-154, 275 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 7

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1256 | 286T1256 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | | | |
| 108 | 20 | | PA | 6-4 | 21-45-22 | D06814J | | 2 | | | | | GD04964 | A.. | E | | 155-199, 276-299 |
| 109 | 18 | | PA | 3-7 | 21-45-22 | D06814J | | 3 | DK | | | | GD02066 | S.. | E | | 050-099 |
| 109 | 18 | | PA | 5-0 | 21-45-22 | D06814J | | 3 | DK | | | | GD02066 | S.. | E | | 150-154 |
| 109 | 18 | | PA | 3-9 | 21-45-22 | D06814J | | 3 | DK | | | | GD02066 | S.. | E | | 155-199, 276-299 |
| 109 | 18 | | PA | 7-0 | 21-45-22 | D06814J | | 3 | DK | | | | GD02066 | S.. | E | | 275 |
| 111 | 22 | | PA | 25-0 | 21-45-22 | D06816J | | 1 | | | | | SM00006 | | 9 | | 150-154, 275 |
| 111 | 22 | | PA | 13-2 | 21-45-22 | D06816J | | 1 | | | | | SM00006 | | 9 | | 155-199, 276-299 |
| 112 | 20 | | PA | 25-0 | 21-45-22 | D06816J | | 2 | | | | | GD04660 | A.. | E | | 150-154, 275 |
| 112 | 20 | | PA | 14-10 | 21-45-22 | D06816J | | 2 | | | | | GD04660 | A.. | E | | 155-199, 276-299 |
| 113 | 18 | | PA | 10-0 | 21-45-22 | D06816J | | 3 | DK | | | | GD04632 | S.. | E | | 150-154, 275 |
| 113 | 18 | | PA | 3-8 | 21-45-22 | D06816J | | 3 | DK | | | | GD04632 | S.. | E | | 155-199, 276-299 |
| 602 | 16 | | PA | 103-0 | 30-71-24 | D06304P | | 12 | FM | | | | SP03687 | | 9 | | 050-099 |
| 602 | 16 | | PA | 122-4 | 30-71-24 | SP03688 | | | 9 | | | | D06304P | | 12 | | 150-154 |
| 602 | 16 | | PA | 121-6 | 30-71-24 | SP03688 | | | 9 | | | | D06304P | | 12 | | 155-199 |
| 814 | 22 | | PA | 135-4 | SPARE | D05820P | | 23 | | | | | D05874J | | 10 | | 150-154, 275 |
| 814 | 22 | | PA | 135-5 | SPARE | D05820P | | 23 | | | | | D05874J | | 10 | | 155-199, 276-299 |
| 815 | 20 | | PA | 113-9 | SPARE | D05820P | | 24 | | | | | D05874J | | 11 | | 050-099 |
| 815 | 20 | | PA | 135-4 | SPARE | D05820P | | 24 | | | | | D05874J | | 11 | | 150-154, 275 |
| 815 | 20 | | PA | 135-5 | SPARE | D05820P | | 24 | | | | | D05874J | | 11 | | 155-199, 276-299 |
| W1258 | 286T1258 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS | | | | | | | | | | | | | |
| 001 | 20 | | PA | 20-8 | 30-71-21 | D05946P | | 1 | | | | | SP00372 | | 9 | | 050-099 |
| 001 | 20 | | PA | 20-7 | 30-71-21 | D05946P | | 1 | | | | | SP00372 | | 9 | | 150-199 |
| 001 | 22 | | PA | 20-7 | 30-71-21 | D05946P | | 1 | | | | | SP00372 | | 9 | | 275-299 |
| 002 | 20 | | PA | 20-8 | 30-71-21 | D05946P | | 2 | | | | | SP00376 | | 9 | | 050-099 |
| 002 | 20 | | PA | 20-7 | 30-71-21 | D05946P | | 2 | | | | | SP00376 | | 9 | | 150-199 |
| 002 | 22 | | PA | 20-7 | 30-71-21 | D05946P | | 2 | | | | | SP00376 | | 9 | | 275-299 |
| 003 | 20 | | PA | 20-8 | 30-71-21 | D05946P | | 3 | | | | | SP00382 | | 9 | | 050-099 |
| 003 | 20 | | PA | 20-7 | 30-71-21 | D05946P | | 3 | | | | | SP00382 | | 9 | | 150-199 |
| 003 | 22 | | PA | 20-7 | 30-71-21 | D05946P | | 3 | | | | | SP00382 | | 9 | | 275-299 |
| 004 | 22 | | PA | 51-7 | 30-71-21 | D05946P | | 4 | | | | | SP00386 | | 9 | | 050-099 |
| 004 | 20 | | PA | 65-2 | 30-71-21 | D05946P | | 4 | | | | | SP00386 | | 9 | | 150-199 |
| 004 | 22 | | PA | 64-4 | 30-71-21 | D05946P | | 4 | | | | | SP00386 | | 9 | | 275-299 |
| 005 | 22 | | PA | 51-7 | 30-71-21 | D05946P | | 5 | | | | | SP00390 | | 9 | | 050-099 |
| 005 | 20 | | PA | 51-10 | 30-71-21 | D05946P | | 5 | | | | | SP00390 | | 9 | | 150-199 |
| 005 | 22 | | PA | 51-9 | 30-71-21 | D05946P | | 5 | | | | | SP00390 | | 9 | | 275-299 |
| 006 | 20 | | PA | 19-8 | 30-71-21 | D05946P | | 6 | | | | | SP00394 | | 9 | | 050-099 |
| 006 | 20 | | PA | 19-7 | 30-71-21 | D05946P | | 6 | | | | | SP00394 | | 9 | | 150-199 |
| 006 | 22 | | PA | 19-7 | 30-71-21 | D05946P | | 6 | | | | | SP00394 | | 9 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|--------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1258 | 286T1258 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | |
| 007 | 20 | | PA | | 14-8 | 30-71-21 | SP00432 | | | | 9 | | | | 050-099 |
| 007 | 20 | | PA | | 14-2 | 30-71-21 | SP00432 | | | | 9 | | | | 150-199 |
| 007 | 20 | | PA | | 14-7 | 30-71-21 | SP00432 | | | | 9 | | | | 275-299 |
| 014 | 20 | | PA | | 93-0 | 30-71-22 | D05690P | | | 1 | | | | | 050-099 |
| 014 | 22 | | PA | | 102-7 | 30-71-22 | D05690P | | | 1 | | | | | 150-154 |
| 014 | 20 | | PA | | 102-7 | 30-71-22 | D05690P | | | 1 | | | | | 155-199 |
| 014 | 22 | | PA | | 103-0 | 30-71-22 | D05690P | | | 1 | | | | | 275-278 |
| 014 | 22 | | PA | | 102-8 | 30-71-22 | D05690P | | | 1 | | | | | 280-299 |
| 015 | 20 | | PA | | 93-0 | 30-71-22 | D05690P | | | 2 | | | | | 050-099 |
| 015 | 22 | | PA | | 102-7 | 30-71-22 | D05690P | | | 2 | | | | | 150-199 |
| 015 | 22 | | PA | | 103-0 | 30-71-22 | D05690P | | | 2 | | | | | 275-278 |
| 015 | 22 | | PA | | 102-8 | 30-71-22 | D05690P | | | 2 | | | | | 280-299 |
| 016 | 20 | | PA | | 81-11 | 30-71-22 | D05690P | | | 3 | | | | | 050-099 |
| 016 | 22 | | PA | | 91-8 | 30-71-22 | D05690P | | | 3 | | | | | 150-154, 275-299 |
| 016 | 20 | | PA | | 91-8 | 30-71-22 | D05690P | | | 3 | | | | | 155-199 |
| 017 | 20 | | PA | | 60-4 | 30-71-21 | D05690P | | | 4 | | | | | 050-099 |
| 017 | 22 | | PA | | 59-6 | 30-71-22 | D05690P | | | 12 | | | | | 150-154 |
| 017 | 20 | | PA | | 59-6 | 30-71-22 | D05690P | | | 12 | | | | | 155-199 |
| 017 | 22 | | PA | | 73-8 | 30-71-22 | D05690P | | | 4 | | | | | 275-299 |
| 018 | 20 | | PA | | 59-4 | 30-71-11 | D05692P | | | 11 | | | | | 050-099 |
| 018 | 20 | | PA | | 74-11 | 30-71-11 | D05692P | | | 11 | | | | | 150-199 |
| 018 | 20 | | PA | | 74-4 | 30-71-11 | D05692P | | | 11 | | | | | 275-299 |
| 019 | 20 | | PA | | 48-7 | 30-71-21 | D05690P | | | 5 | | | | | 050-099 |
| 020 | 20 | | PA | | 48-7 | 30-71-21 | D05690P | | | 6 | | | | | 050-099 |
| 021 | 20 | | PA | | 28-7 | 30-71-21 | D05690P | | | 7 | | | | | 050-099 |
| 021 | 20 | | PA | | 28-1 | 30-71-21 | D05690P | | | 7 | | | | | 150-199 |
| 021 | 22 | | PA | | 28-6 | 30-71-21 | D05690P | | | 7 | | | | | 275-299 |
| 022 | 20 | | PA | | 45-10 | 30-71-21 | D05690P | | | 8 | | | | | 050-099 |
| 027 | 20 | | PA | | 12-11 | 30-71-22 | SP03644 | | | | 9 | | | | 150-199 |
| 027 | 20 | | PA | | 12-8 | 30-71-22 | SP00414 | | | | 9 | | | | 275-299 |
| 028 | 20 | | PA | | 17-8 | 30-71-22 | SP00418 | | | | 9 | | | | 275-299 |
| 029 | 20 | | PA | | 9-8 | 30-71-22 | GD04404 | | A.. | E | | | | | 050-099 |
| 029 | 20 | | PA | | 7-7 | 30-71-22 | SP00420 | | | | 9 | | | | 150-199 |
| 034 | 20 | | PA | | 131-6 | 30-71-23 | D05690P | | | 9 | | | | | 050-099 |
| 034 | 20 | | PA | | 152-5 | 30-71-23 | D05690P | | | 9 | | | | | 150-199, 275-276 |
| 034 | 22 | | PA | | 152-5 | 30-71-23 | D05690P | | | 9 | | | | | 277-299 |
| 035 | 20 | | PA | | 137-10 | 30-71-24 | D05692P | | | 10 | | | | | 050-099 |
| 035 | 22 | | PA | | 152-5 | 30-71-23 | D05690P | | | 10 | | | | | 150-154, 275-299 |
| 035 | 20 | | PA | | 152-5 | 30-71-23 | D05690P | | | 10 | | | | | 155-199 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1258 | 286T1258 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | | | |
| 036 | 20 | | PA | 131-6 | 30-71-23 | D05690P | | 11 | | | | | D06308P | 3 | | | 050-099 |
| 036 | 22 | | PA | 152-5 | 30-71-23 | D05690P | | 11 | | | | | D06308P | 3 | | | 150-154, 275-299 |
| 036 | 20 | | PA | 152-5 | 30-71-23 | D05690P | | 11 | | | | | D06308P | 3 | | | 155-199 |
| 043 | 20 | | PA | 125-11 | 30-71-23 | D05690P | | 31 | | | | | SP00456 | | 9 | | 050-099 |
| 043 | 20 | | PA | 147-2 | 30-71-24 | D05692P | | 2 | | | | | SP00456 | | 9 | | 150-199 |
| 050 | 20 | | PA | 137-10 | 21-31-21 | D06308P | | 18 | | | | | D05692P | 7 | | | 050-099 |
| 050 | 20 | | PA | 158-8 | 21-31-21 | D06308P | | 18 | | | | | D05692P | 7 | | | 150-199 |
| 050 | 20 | | PA | 158-9 | 21-31-21 | D06308P | | 18 | | | | | D05692P | 7 | | | 275-299 |
| 053 | 20 | | PA | 10-7 | 30-71-11 | SP00368 | | | | 9 | | | GD05420 | A.. | E | | 150-199 |
| 053 | 20 | | PA | 10-11 | 30-71-11 | SP00368 | | | | 9 | | | GD05420 | A.. | E | | 275-299 |
| 055 | 22 | | PA | 84-4 | 30-71-22 | D05946P | | 14 | | | | | SP00620 | | 9 | | 275-299 |
| 057 | 22 | | PA | 137-7 | 30-71-23 | D05690P | | 14 | | | | | SP00624 | | 9 | | 150-154 |
| 057 | 20 | | PA | 137-7 | 30-71-23 | D05690P | | 14 | | | | | SP00624 | | 9 | | 155-199 |
| 057 | 22 | | PA | 152-5 | 30-71-23 | D05690P | | 14 | | | | | D06308P | 5 | | | 275-276 |
| 057 | 22 | | PA | 132-5 | 30-71-23 | D05690P | | 14 | | | | | SP04006 | | 9 | | 277-299 |
| 058 | 20 | | PA | 131-6 | 30-71-23 | D05690P | | 15 | | | | | D06308P | 6 | | | 050-099 |
| 058 | 22 | | PA | 152-5 | 30-71-23 | D05690P | | 15 | | | | | D06308P | 6 | | | 150-154, 275-299 |
| 058 | 20 | | PA | 152-5 | 30-71-23 | D05690P | | 15 | | | | | D06308P | 6 | | | 155-199 |
| 059 | 20 | | PA | 64-6 | 30-71-22 | D05690P | | 16 | | | | | SP00416 | | 9 | | 050-099 |
| 059 | 22 | | PA | 74-4 | 30-71-22 | D05690P | | 16 | | | | | SP00416 | | 9 | | 150-154 |
| 059 | 20 | | PA | 74-4 | 30-71-22 | D05690P | | 16 | | | | | SP00416 | | 9 | | 155-199 |
| 060 | 20 | | PA | 131-6 | 30-71-23 | D05690P | | 14 | | | | | D06308P | 4 | | | 050-099 |
| 060 | 20 | | PA | 158-8 | 30-71-24 | D05692P | | 10 | | | | | D06308P | 4 | | | 150-199 |
| 061 | 20 | | PA | 20-9 | 30-71-21 | D05946P | | 8 | | | | | SP01640 | | 9 | | 050-099 |
| 061 | 20 | | PA | 20-8 | 30-71-21 | D05946P | | 8 | | | | | SP01640 | | 9 | | 150-199 |
| 061 | 22 | | PA | 20-8 | 30-71-21 | D05946P | | 8 | | | | | SP01640 | | 9 | | 275-299 |
| 063 | 20 | | PA | 20-9 | 30-71-21 | D05946P | | 10 | | | | | SP01644 | | 9 | | 050-099 |
| 063 | 20 | | PA | 20-8 | 30-71-21 | D05946P | | 10 | | | | | SP01644 | | 9 | | 150-199 |
| 063 | 22 | | PA | 20-8 | 30-71-21 | D05946P | | 10 | | | | | SP01644 | | 9 | | 275-299 |
| 067 | 20 | | PA | 58-7 | 30-71-22 | D05690P | | 17 | | | | | SP01652 | | 9 | | 050-099 |
| 068 | 20 | | PA | 7-4 | 30-71-22 | SP01654 | | | | 9 | | | GD03554 | A.. | 2 | | 050-099 |
| 069 | 20 | | PA | 19-2 | 30-71-21 | D05946P | | 11 | | | | | SP01794 | | 9 | | 050-099, 150-199 |
| 069 | 22 | | PA | 19-1 | 30-71-21 | D05946P | | 11 | | | | | SP01794 | | 9 | | 275-299 |
| 074 | 22 | | PA | 78-2 | 30-71-22 | D05946P | | 15 | | | | | SP02158 | | 9 | | 150-199 |
| 076 | 20 | | PA | 64-5 | 30-71-22 | D05946P | | 16 | | | | | SP02146 | | 9 | | 050-099 |
| 076 | 22 | | PA | 74-2 | 30-71-22 | D05946P | | 16 | | | | | SP02146 | | 9 | | 150-199, 275-299 |
| 077 | 20 | | PA | 10-8 | 30-71-22 | SP02148 | | | | 9 | | | GD03554 | A.. | 2 | | ALL |
| 078 | 20 | | PA | 62-10 | 30-71-22 | D05946P | | 17 | | | | | SP02162 | | 9 | | 050-099 |
| 078 | 22 | | PA | 72-8 | 30-71-22 | D05946P | | 17 | | | | | SP02162 | | 9 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1258 | 286T1258 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | |
| 079 | 20 | | PA | 9-1 | 30-71-22 | SP02164 | | | 9 | | GD03554 | A.. | 2 | | 050-099 |
| 079 | 20 | | PA | 10-8 | 30-71-22 | SP02164 | | | 9 | | GD04404 | A.. | E | | 150-199 |
| 080 | 20 | | PA | 93-0 | 30-71-22 | D05690P | | 19 | | | SP01836 | | 9 | | 050-099 |
| 080 | 22 | | PA | 102-7 | 30-71-22 | D05690P | | 19 | | | SP01836 | | 9 | | 150-154 |
| 080 | 20 | | PA | 102-7 | 30-71-22 | D05690P | | 19 | | | SP01836 | | 9 | | 155-199 |
| 082 | 20 | | PA | 64-5 | 30-71-22 | D05946P | | 18 | | | SP02150 | | 9 | | 050-099 |
| 082 | 22 | | PA | 74-2 | 30-71-22 | D05946P | | 18 | | | SP02150 | | 9 | | 150-154, 275-299 |
| 082 | 20 | | PA | 74-2 | 30-71-22 | D05946P | | 18 | | | SP02150 | | 9 | | 155-199 |
| 083 | 20 | | PA | 10-8 | 30-71-22 | SP02152 | | | 9 | | GD03554 | A.. | 2 | | ALL |
| 086 | 20 | | PA | 61-1 | 30-71-22 | D05946P | | 13 | | | SP02166 | | 9 | | 050-099 |
| 086 | 22 | | PA | 74-8 | 30-71-22 | D05946P | | 13 | | | SP02166 | | 9 | | 150-199, 275-299 |
| 087 | 20 | | PA | 7-4 | 30-71-22 | GD03554 | | | A.. | 2 | SP02168 | | 9 | | 050-099 |
| 087 | 20 | | PA | 11-2 | 30-71-22 | GD03554 | | | A.. | 2 | SP02168 | | 9 | | 150-199, 275-299 |
| 088 | 22 | | PA | 74-2 | 30-71-22 | D05946P | | 14 | | | SP02170 | | 9 | | 150-154 |
| 088 | 20 | | PA | 74-2 | 30-71-22 | D05946P | | 14 | | | SP02170 | | 9 | | 155-199 |
| 089 | 20 | | PA | 10-8 | 30-71-22 | SP02172 | | | 9 | | GD03554 | A.. | 2 | | 150-199 |
| 097 | 16 | | PA | 137-10 | 30-71-24 | D05692P | | 21 | | | D06308P | | 15 | | 050-099 |
| 097 | 16 | | PA | 158-8 | 30-71-24 | D05692P | | 21 | | | D06308P | | 15 | | 150-199 |
| 132 | 22 | | PA | 76-7 | 30-71-22 | D05946P | | 27 | | | SP02456 | | 9 | | 150-199 |
| 133 | 20 | | PA | 66-9 | 30-71-22 | D05946P | | 28 | | | SP02458 | | 9 | | 050-099 |
| 133 | 22 | | PA | 77-10 | 30-71-22 | D05946P | | 28 | | | SP02458 | | 9 | | 150-199 |
| 138 | 20 | | PA | 7-5 | 30-71-22 | SP02476 | | | 9 | | GD04406 | A.. | E | | 150-199 |
| 142 | 22 | | PA | 84-4 | 30-71-22 | D05946P | | 28 | | | SP03070 | | 9 | | 275-299 |
| 144 | 20 | | PA | 17-8 | 30-71-22 | SP03072 | | | 9 | | GD04410 | A.. | E | | 275-299 |
| 145 | 20 | | PA | 93-0 | 30-71-23 | D05690P | | 30 | | | SP00438 | | 9 | | 050-099 |
| 145 | 20 | | PA | 108-11 | 30-71-24 | D05692P | | 13 | | | SP00438 | | 9 | | 150-199 |
| 146 | 20 | | PA | 17-5 | 30-71-23 | GD01146 | | | A.. | E | SP00458 | | 9 | | 050-099 |
| 146 | 20 | | PA | 13-1 | 30-71-24 | SP00458 | | | 9 | | GD01146 | A.. | E | | 150-199 |
| 147 | 20 | | PA | 9-9 | 30-71-23 | SP00448 | | | 9 | | GD01146 | A.. | E | | 150-199 |
| 150 | 20 | | PA | 71-1 | 30-71-22 | D05690P | | 25 | | | SP02710 | | 9 | | 050-099 |
| 150 | 22 | | PA | 81-10 | 30-71-22 | D05690P | | 25 | | | SP02710 | | 9 | | 275-299 |
| 164 | 20 | | PA | 12-7 | 30-71-22 | SP02628 | | | 9 | | GD04376 | A.. | E | | 050-099 |
| 165 | 20 | | PA | 77-4 | 30-71-21 | D05690P | | 35 | | | SP03240 | | 9 | | 150-199 |
| 166 | 20 | | PA | 62-8 | 30-71-21 | D05690P | | 36 | | | SP03242 | | 9 | | 150-199 |
| 166 | 22 | | PA | 61-10 | 30-71-21 | D05690P | | 36 | | | SP03242 | | 9 | | 275-299 |
| 167 | 20 | | PA | 7-1 | 30-71-21 | SP03246 | | | 9 | | GD04764 | A.. | 2 | | 150-199 |
| 169 | 20 | | PA | 23-0 | 30-71-21 | D05690P | | 23 | | | SP03250 | | 9 | | 050-099 |
| 169 | 20 | | PA | 28-1 | 30-71-21 | D05690P | | 23 | | | SP03250 | | 9 | | 150-199 |
| 170 | 20 | | PA | 26-0 | 30-71-21 | D05690P | | 37 | | | SP03254 | | 9 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 11

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1258 | 286T1258 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | | | |
| 170 | 20 | | PA | 26-3 | 30-71-21 | D05690P | | 37 | | | | | SP03254 | | 9 | | 150-199 |
| 170 | 22 | | PA | 26-3 | 30-71-21 | D05690P | | 37 | | | | | SP03254 | | 9 | | 275-299 |
| 171 | 20 | | PA | 6-6 | 30-71-21 | SP03252 | | | 9 | | | | GD04332 | A.. | E | | 050-099 |
| 171 | 20 | | PA | 14-2 | 30-71-21 | SP03252 | | | 9 | | | | GD04332 | A.. | E | | 150-199 |
| 172 | 20 | | PA | 9-6 | 30-71-21 | SP03256 | | | 9 | | | | GD04332 | A.. | E | | 050-099 |
| 172 | 20 | | PA | 9-10 | 30-71-21 | SP03256 | | | 9 | | | | GD04332 | A.. | E | | 150-199, 275-299 |
| 174 | 20 | | PA | 20-9 | 30-71-21 | D05946P | | 40 | | | | | SP03530 | | 9 | | 050-099 |
| 174 | 22 | | PA | 21-3 | 30-71-21 | D05946P | | 40 | | | | | SP03530 | | 9 | | 150-154 |
| 174 | 20 | | PA | 21-3 | 30-71-21 | D05946P | | 40 | | | | | SP03530 | | 9 | | 155-199 |
| 176 | 20 | | PA | 21-7 | 30-71-21 | SP03534 | | | 9 | | | | GD05546 | A.. | E | | 150-199 |
| 177 | 20 | | PA | 21-7 | 30-71-21 | SP03536 | | | 9 | | | | GD05546 | A.. | E | | 150-199 |
| 183 | 20 | | PA | 29-6 | 30-71-21 | D05946P | | 22 | | | | | SP03646 | | 9 | | 050-099 |
| 183 | 20 | | PA | 29-2 | 30-71-21 | D05946P | | 22 | | | | | SP03646 | | 9 | | 150-199 |
| 184 | 20 | | PA | 29-6 | 30-71-21 | D05946P | | 21 | | | | | SP03648 | | 9 | | 050-099 |
| 184 | 20 | | PA | 29-2 | 30-71-21 | D05946P | | 21 | | | | | SP03648 | | 9 | | 150-199 |
| 185 | 20 | | PA | 29-6 | 30-71-21 | D05946P | | 20 | | | | | SP03650 | | 9 | | 050-099 |
| 185 | 20 | | PA | 29-2 | 30-71-21 | D05946P | | 20 | | | | | SP03650 | | 9 | | 150-199 |
| 187 | 20 | | PA | 29-6 | 30-71-21 | D05946P | | 19 | | | | | SP03652 | | 9 | | 050-099 |
| 187 | 20 | | PA | 29-2 | 30-71-21 | D05946P | | 19 | | | | | SP03652 | | 9 | | 150-199 |
| 188 | 20 | | PA | 62-0 | 30-71-21 | D05946P | | 23 | | | | | SP03654 | | 9 | | 150-199 |
| 189 | 22 | | PQ | JL | 67-2 | 21-28-11 | D13568 | | 1 | | | | D05692P | | 19 | | 050-099 |
| 189 | 22 | | PA | | 66-4 | 21-28-11 | D13568 | | 1 | | | | D05692P | | 19 | | 150-199 |
| 189 | 22 | | PA | | 66-11 | 21-28-11 | D13568 | | 1 | | | | D05692P | | 19 | | 275-276 |
| 189Z | | | JL | | 0-0 | 21-28-11 | D13568 | DED | | | | | D05692P | DED | | | 050-099 |
| 190 | 22 | | PQ | JN | 67-2 | 21-28-11 | D13568 | | 2 | | | | D05692P | | 18 | | 050-099 |
| 190 | 22 | | PA | | 66-4 | 21-28-11 | D13568 | | 2 | | | | D05692P | | 18 | | 150-199 |
| 190 | 22 | | PA | | 66-11 | 21-28-11 | D13568 | | 2 | | | | D05692P | | 18 | | 275-276 |
| 190Z | | | JN | | 0-0 | 21-28-11 | D13568 | DED | | | | | D05692P | DED | | | 050-099 |
| 191 | 20 | | PA | | 18-11 | 21-28-11 | D13568 | | 5 | | | | GD04396 | S.. | 2 | | 050-099 |
| 191 | 20 | | PA | | 7-10 | 21-28-11 | D13568 | | 5 | | | | GD05682 | S.. | 2 | | 150-199 |
| 191 | 20 | | PA | | 8-3 | 21-28-11 | D13568 | | 5 | | | | GD05682 | S.. | 2 | | 275-276 |
| 192 | 24 | | PK | | 67-2 | 21-28-11 | D13568 | | 8 | | | | D05692P | | 1 | | 050-099 |
| 192 | 24 | | PK | | 66-4 | 21-28-11 | D13568 | | 8 | | | | D05692P | | 1 | | 150-199 |
| 192 | 24 | | PK | | 66-11 | 21-28-11 | D13568 | | 8 | | | | D05692P | | 1 | | 275-276 |
| 193 | 20 | | PA | | 18-11 | 21-28-11 | D13568 | | 9 | | | | GD04396 | D.. | 2 | | 050-099 |
| 193 | 20 | | PA | | 7-10 | 21-28-11 | D13568 | | 9 | | | | GD05682 | D.. | 2 | | 150-199 |
| 193 | 20 | | PA | | 8-3 | 21-28-11 | D13568 | | 9 | | | | GD05682 | D.. | 2 | | 275-276 |
| 194 | 22 | | PA | | 66-9 | 21-28-11 | D13566 | | 1 | | | | D05692P | | 22 | | 050-099 |
| 194 | 22 | | PA | | 65-9 | 21-28-11 | D13566 | | 1 | | | | D05692P | | 22 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1258 | 286T1258 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | |
| 194 | 22 | | PA | 66-3 | 21-28-11 | D13566 | | 1 | | | D05692P | 22 | | | 275-299 |
| 195 | 22 | | PA | 66-9 | 21-28-11 | D13566 | | 2 | | | D05692P | 20 | | | 050-099 |
| 195 | 22 | | PA | 65-9 | 21-28-11 | D13566 | | 2 | | | D05692P | 20 | | | 150-199 |
| 195 | 22 | | PA | 66-3 | 21-28-11 | D13566 | | 2 | | | D05692P | 20 | | | 275-299 |
| 196 | 20 | | PA | 16-7 | 21-28-11 | D13566 | | 3 | | | GD04394 | D.. | 2 | | 050-099 |
| 196 | 20 | | PA | 7-3 | 21-28-11 | D13566 | | 3 | | | GD05682 | D.. | 2 | | 150-199 |
| 196 | 20 | | PA | 7-8 | 21-28-11 | D13566 | | 3 | | | GD05682 | D.. | 2 | | 275-299 |
| 197 | 20 | | PA | 16-7 | 21-28-11 | D13566 | | 5 | | | GD04394 | S.. | 2 | | 050-099 |
| 197 | 20 | | PA | 7-3 | 21-28-11 | D13566 | | 5 | | | GD05682 | S.. | 2 | | 150-199 |
| 197 | 20 | | PA | 7-8 | 21-28-11 | D13566 | | 5 | | | GD05682 | S.. | 2 | | 275-299 |
| 198 | 20 | | PA | 16-7 | 21-28-11 | D13566 | | 8 | | | GD04394 | D.. | 2 | | 050-099 |
| 198 | 20 | | PA | 7-3 | 21-28-11 | D13566 | | 8 | | | GD05682 | D.. | 2 | | 150-199 |
| 198 | 20 | | PA | 7-8 | 21-28-11 | D13566 | | 8 | | | GD05682 | D.. | 2 | | 275-299 |
| 199 | 24 | | PK | 66-9 | 21-28-11 | D13566 | | 9 | | | D05692P | 24 | | | 050-099 |
| 199 | 24 | | PK | 65-9 | 21-28-11 | D13566 | | 9 | | | D05692P | 24 | | | 150-199 |
| 199 | 24 | | PK | 66-3 | 21-28-11 | D13566 | | 9 | | | D05692P | 24 | | | 275-299 |
| 201B | 24 | | PW | AR | 137-10 | 21-31-21 | D05692P | 5 | | | D06308P | 20 | | | 050-099 |
| 201B | 24 | | PW | AR | 158-8 | 21-31-21 | D05692P | 5 | | | D06308P | 20 | | | 150-199 |
| 201B | 24 | | PW | AR | 158-9 | 21-31-21 | D05692P | 5 | | | D06308P | 20 | | | 275-299 |
| 201R | 24 | | PW | AR | 0-0 | 21-31-21 | D05692P | 6 | | | D06308P | 21 | | | ALL |
| 201Z | | | | AR | 0-0 | 21-31-21 | D05692P | 4 | | | D06308P | 7 | | | ALL |
| 202B | 20 | | PB | AS | 137-10 | 21-31-21 | D06308P | 22 | | | D05692P | 8 | | | 050-099 |
| 202B | 20 | | PB | AS | 158-8 | 21-31-21 | D06308P | 22 | | | D05692P | 8 | | | 150-199 |
| 202B | 20 | | PB | AS | 158-9 | 21-31-21 | D06308P | 22 | | | D05692P | 8 | | | 275-299 |
| 202R | 20 | | PB | AS | 0-0 | 21-31-21 | D06308P | 24 | | | D05692P | 9 | | | ALL |
| 211 | 20 | | PA | | 21-3 | 30-71-21 | D05946P | 33 | | | SP03974 | | 9 | | 155-199 |
| 500 | 20 | | PA | | 137-10 | SPARE | D05692P | 14 | | | D06308P | 25 | | | 050-099 |
| 500 | 20 | | PA | | 158-8 | SPARE | D05692P | 25 | | | D06308P | 25 | | | 155, 162-165 |
| 507 | 20 | | PA | | 137-10 | SPARE | D05692P | 13 | | | D06308P | 26 | | | 050-099 |
| 507 | 20 | | PA | | 158-8 | SPARE | D05692P | 3 | | | D06308P | 26 | | | 155, 162-165 |
| 509 | 20 | | PA | | 12-7 | 30-71-22 | SP05080 | | 9 | | GD04412 | A.. | E | | 050-099 |
| 600 | 20 | | PA | | 20-8 | 30-71-21 | D05946P | 32 | | | SP03368 | | 9 | | 050-099 |
| 600 | 20 | | PA | | 20-7 | 30-71-21 | D05946P | 32 | | | SP03368 | | 9 | | 150-199 |
| 602 | 20 | | PA | | 65-5 | 30-71-21 | D05946P | 34 | | | SP03372 | | 9 | | 150-199 |
| 603 | 20 | | PA | | 71-4 | 30-71-21 | D05946P | 35 | | | SP03532 | | 9 | | 150-199 |
| 604 | 20 | | PA | | 71-4 | 30-71-21 | D05946P | 36 | | | SP03538 | | 9 | | 150-199 |
| 606 | 20 | | PA | | 60-10 | 30-71-21 | D05946P | 38 | | | SP03380 | | 9 | | 150-199 |
| 607 | 24 | | PK | | 13-8 | 21-26-31 | D13568 | 7 | | | SM00002 | | S | | 050-099 |
| 607 | 24 | | PK | | 66-4 | 21-26-31 | D13568 | 7 | | | SM00002 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 13

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1258 | 286T1258 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | | | |
| 607 | 24 | | PK | 66-11 | 21-26-31 | D13568 | 7 | | | | | | SM00002 | | S | | 275-276 |
| 607 | 24 | | PK | 67-8 | 21-26-31 | SM00002 | | | | | S | | SP05300 | | 9 | | 277-278 |
| 607 | 24 | | PK | 67-8 | 21-26-31 | SP05300 | | | | | 9 | | SM00002 | | S | | 280-299 |
| 608 | 20 | | PA | 16-7 | 21-26-31 | D13566 | 6 | | | | | | GD04394 | D.. | 2 | | 050-099 |
| 608 | 20 | | PA | 7-3 | 21-26-31 | D13566 | 6 | | | | | | GD05682 | D.. | 2 | | 150-199 |
| 608 | 20 | | PA | 7-8 | 21-26-31 | D13566 | 6 | | | | | | GD05682 | D.. | 2 | | 275-276 |
| 608 | 20 | | PA | 7-8 | 21-28-11 | D13566 | 6 | | | | | | GD05682 | D.. | 2 | | 277-299 |
| 609 | 24 | | PK | 2-10 | 21-26-31 | D13566 | 7 | | | | | | D13568 | | 6 | | 050-099 |
| 609 | 24 | | PK | 2-11 | 21-26-31 | D13566 | 7 | | | | | | D13568 | | 6 | | 150-199, 275-276 |
| 609 | 24 | | PK | 5-0 | 21-28-11 | D13566 | 7 | | | | | | SP05298 | | 9 | | 277-278 |
| 609 | 24 | | PK | 3-8 | 21-28-11 | D13566 | 7 | | | | | | SP05298 | | 9 | | 280-299 |
| 610 | 24 | | PK | 54-6 | 21-26-31 | D05692P | 17 | | | | | | SM00002 | | S | | 050-099 |
| 610 | 24 | | PK | 0-7 | 21-26-31 | D05692P | 17 | | | | | | SM00002 | | S | | 150-199, 275-299 |
| 611 | 22 | | PA | 67-4 | 21-26-31 | D13576 | 2 | | | | | | D05692P | | 2 | | 050-099 |
| 611 | 22 | | PA | 66-2 | 21-26-31 | D13576 | 2 | | | | | | D05692P | | 14 | | 150-199 |
| 611 | 22 | | PA | 66-7 | 21-26-31 | D13576 | 2 | | | | | | D05692P | | 14 | | 275-299 |
| 612 | 22 | | PA | 67-4 | 21-26-31 | D13576 | 3 | | | | | | D05692P | | 15 | | 050-099 |
| 612 | 22 | | PA | 66-2 | 21-26-31 | D13576 | 3 | | | | | | D05692P | | 15 | | 150-199 |
| 612 | 22 | | PA | 66-7 | 21-26-31 | D13576 | 3 | | | | | | D05692P | | 15 | | 275-299 |
| 613 | 22 | | PA | 67-4 | 21-26-31 | D13576 | 1 | | | | | | D05692P | | 12 | | 050-099 |
| 613 | 22 | | PA | 66-2 | 21-26-31 | D13576 | 1 | | | | | | D05692P | | 12 | | 150-199 |
| 613 | 22 | | PA | 66-7 | 21-26-31 | D13576 | 1 | | | | | | D05692P | | 12 | | 275-299 |
| 614 | 24 | | PK | 67-4 | 21-26-31 | D13576 | 5 | | | | | | D05692P | | 16 | | 050-099 |
| 614 | 24 | | PK | 66-2 | 21-26-31 | D13576 | 5 | | | | | | D05692P | | 16 | | 150-199 |
| 614 | 24 | | PK | 66-7 | 21-26-31 | D13576 | 5 | | | | | | D05692P | | 16 | | 275-299 |
| 615 | 24 | | PK | 13-10 | 21-26-31 | D13576 | 6 | | | | | | SM00002 | | S | | 050-099 |
| 615 | 24 | | PK | 66-2 | 21-26-31 | D13576 | 6 | | | | | | SM00002 | | S | | 150-199 |
| 615 | 24 | | PK | 66-7 | 21-26-31 | D13576 | 6 | | | | | | SM00002 | | S | | 275-299 |
| 616 | 20 | | PA | 17-3 | 21-26-31 | D13576 | 7 | | | | | | GD04394 | S.. | 2 | | 050-099 |
| 616 | 20 | | PA | 7-8 | 21-26-31 | D13576 | 7 | | | | | | GD05682 | S.. | 2 | | 150-199 |
| 616 | 20 | | PA | 7-11 | 21-26-31 | D13576 | 7 | | | | | | GD05682 | S.. | 2 | | 275-299 |
| 617 | 20 | | PQ | JM | 18-11 | 21-28-11 | D13568 | 3 | | | | | GD04396 | D.. | 2 | | 050-099 |
| 617 | 20 | | PA | | 7-10 | 21-28-11 | D13568 | 3 | | | | | GD05682 | D.. | 2 | | 150-199 |
| 617 | 20 | | PA | | 8-3 | 21-28-11 | D13568 | 3 | | | | | GD05682 | D.. | 2 | | 275-276 |
| 617Z | | | | JM | 0-0 | 21-28-11 | D13568 | | DED | | | | GD04396 | DED | | | 050-099 |
| 618 | 16 | | PA | 26-0 | 30-71-24 | D05692P | 23 | | | | | | SP03687 | | 9 | | 050-099 |
| 618 | 16 | | PA | 13-7 | 30-71-24 | D05692P | 23 | | | | | | SP03688 | | 9 | | 150-199 |
| 629 | 22 | | PA | 73-8 | 30-71-22 | D05690P | 17 | | | | | | SP03932 | | 9 | | 275-299 |
| 630 | 22 | | PA | 76-11 | 30-71-22 | D05690P | 19 | | | | | | SP03934 | | 9 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|----------|---------|---------|-------|------|------|---------|-------|------|------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1258 | 286T1258 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | |
| 631 | 22 | PA | | 76-10 | 30-71-22 | D05946P | | 29 | | | SP03936 | | 9 | | 275-299 |
| 632 | 22 | PA | | 76-2 | 30-71-22 | D05946P | | 17 | | | SP03938 | | 9 | | 275-299 |
| 633 | 20 | PA | | 12-8 | 30-71-22 | SP03940 | | | 9 | | GD03554 | A.. | 2 | | 275-299 |
| 634 | 20 | PA | | 13-8 | 30-71-22 | SP03942 | | | 9 | | GD04408 | A.. | E | | 275-299 |
| 635 | 20 | PA | | 7-7 | 30-71-22 | SP03944 | | | 9 | | GD04404 | A.. | E | | 275-299 |
| 636 | 20 | PA | | 12-8 | 30-71-22 | SP03946 | | | 9 | | GD03554 | A.. | 2 | | 275-299 |
| 639 | 20 | PA | | 9-3 | 30-71-21 | GD04388 | A.. | E | | | SP03956 | | 9 | | 050-099 |
| 639 | 20 | PA | | 10-3 | 30-71-21 | SP03956 | | | 9 | | GD04388 | A.. | E | | 150-199 |
| 640 | 20 | PA | | 9-3 | 30-71-21 | GD04388 | A.. | E | | | SP03958 | | 9 | | 050-099 |
| 640 | 20 | PA | | 10-3 | 30-71-21 | SP03958 | | | 9 | | GD04388 | A.. | E | | 150-199 |
| 641 | 20 | PA | | 9-3 | 30-71-21 | GD04388 | A.. | E | | | SP03960 | | 9 | | 050-099 |
| 641 | 20 | PA | | 10-3 | 30-71-21 | SP03960 | | | 9 | | GD04388 | A.. | E | | 150-199 |
| 642 | 20 | PA | | 9-3 | 30-71-21 | GD04388 | A.. | E | | | SP03962 | | 9 | | 050-099 |
| 642 | 20 | PA | | 11-0 | 30-71-21 | SP03962 | | | 9 | | GD04388 | A.. | E | | 150-199 |
| 643 | 20 | PA | | 5-5 | 30-71-21 | SP03973 | | | 9 | | GD05420 | A.. | E | | 150-199 |
| 644 | 20 | PA | | 14-0 | 30-71-21 | GD05544 | A.. | E | | | SP03978 | | 9 | | 150-153 |
| 644 | 20 | PA | | 13-8 | 30-71-21 | GD05544 | A.. | E | | | SP03978 | | 9 | | 154-199 |
| 646 | 20 | PA | | 20-9 | 30-71-21 | D05946P | | 33 | | | SP03974 | | 9 | | 050-099 |
| 648 | 20 | PA | | 65-2 | 30-71-22 | D05946P | | 7 | | | SP03996 | | 9 | | 050-099 |
| 649 | 20 | PA | | 73-7 | 30-71-22 | D05946P | | 23 | | | SP04000 | | 9 | | 050-099 |
| 651 | 20 | PA | | 93-0 | 30-71-22 | D05690P | | 21 | | | SP04002 | | 9 | | 050-099 |
| 652 | 20 | PA | | 93-0 | 30-71-22 | D05690P | | 35 | | | SP03994 | | 9 | | 050-099 |
| 653 | 20 | PA | | 93-0 | 30-71-22 | D05690P | | 36 | | | SP03998 | | 9 | | 050-099 |
| 655 | 20 | PA | | 128-0 | 30-71-24 | D05692P | | 25 | | | SP04006 | | 9 | | 050-099 |
| 657 | 20 | PA | | 13-2 | 30-71-24 | GD01146 | A.. | E | | | SP04008 | | 9 | | 050-099 |
| 657 | 20 | PA | | 13-4 | 30-71-23 | SP04008 | | | 9 | | GD01146 | A.. | E | | 277-299 |
| 658 | 20 | PA | | 8-8 | 30-71-22 | SP04010 | | | 9 | | GD04406 | A.. | E | | 150-199 |
| 814 | 22 | PA | | 134-0 | SPARE | D05690P | | 38 | | | D06308P | CAP | Y | | 050-099 |
| 814 | 22 | PA | | 153-0 | SPARE | D05690P | | 38 | | | D06308P | CAP | Y | | 150-199, 275-299 |
| 815 | 20 | PA | | 153-0 | SPARE | D05690P | | 39 | | | D06308P | CAP | Y | | 150-199, 275-299 |
| A-A | | | | 0-0 | 30-71-21 | SP00372 | | | 9 | | B00043 | = P | | | 050-099, 150-199, 275-278 |
| A-A | | | | 0-0 | 30-71-21 | B00043 | | = P | | | SP00372 | | 9 | | 280-299 |
| A-B | | | | 0-0 | 30-71-21 | GD04384 | | A.. | E | | B00043 | = G | | | ALL |
| A-M | | | | 0-0 | 30-71-22 | SP03070 | | | 9 | | B00256 | = P | | | 275-299 |
| A-N | | | | 0-0 | 30-71-22 | B00256 | | = G | | | SP03072 | | 9 | | 275-299 |
| A-Q | | | | 0-0 | 30-71-21 | B00346 | | = P | | | SP03368 | | 9 | | 050-099 |
| A-Q | | | | 0-0 | 30-71-21 | SP03368 | | | 9 | | B00346 | = P | | | 150-199 |
| A-R | | | | 0-0 | 30-71-21 | B00346 | | = G | | | GD04384 | A.. | E | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 15

Mar 09/2006



| Bundle No. | | Part Number | | | Description | | | | From | | | | To | | | | |
|--------------|-----------------|-------------|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1258 | 286T1258 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | | | |
| A-W | | | | | 0-0 | 30-71-21 | SP03532 | | | 9 | B00350 | = P | | | 150-199 | | |
| A-X | | | | | 0-0 | 30-71-21 | B00350 | = G | | | SP03534 | | 9 | | 150-199 | | |
| A-Y | | | | | 0-0 | 30-71-21 | SP03538 | | | 9 | B00351 | = P | | | 150-199 | | |
| A-Z | | | | | 0-0 | 30-71-21 | SP01794 | | | 9 | B00133 | = P | | | ALL | | |
| B-A | | | | | 0-0 | 30-71-21 | SP00376 | | | 9 | B00118 | = P | | | ALL | | |
| B-B | | | | | 0-0 | 30-71-21 | GD01056 | A.. | 2 | | B00118 | = G | | | ALL | | |
| B-C | | | | | 0-0 | 30-71-22 | B00234 | = P | | | SP02710 | | 9 | | 050-099, 275-299 | | |
| B-D | | | | | 0-0 | 30-71-22 | B00234 | = G | | | GD04408 | A.. | E | | 050-099, 275-299 | | |
| B-E | | | | | 0-0 | 30-71-22 | B00135 | = P | | | SP02162 | | 9 | | 050-099 | | |
| B-F | | | | | 0-0 | 30-71-22 | B00135 | = G | | | SP02164 | | 9 | | 050-099 | | |
| B-I | | | | | 0-0 | 30-71-21 | B00351 | = G | | | SP03536 | | 9 | | 150-199 | | |
| B-M | | | | | 0-0 | 30-71-21 | SP03380 | | | 9 | B00353 | = P | | | 150-199 | | |
| B-N | | | | | 0-0 | 30-71-21 | B00353 | = G | | | GD05544 | A.. | | | 150-154 | | |
| B-N | | | | | 0-0 | 30-71-21 | B00353 | = G | | | GD05544 | A.. | E | | 155-199 | | |
| B-O | | | | | 0-0 | 30-71-21 | B00347 | = P | | | SP03530 | | 9 | | 050-099 | | |
| B-O | | | | | 0-0 | 30-71-21 | SP03530 | | | 9 | B00347 | = P | | | 150-199 | | |
| B-P | | | | | 0-0 | 30-71-21 | B00347 | = G | | | GD01056 | A.. | 2 | | 050-099 | | |
| B-P | | | | | 0-0 | 30-71-21 | GD01056 | A.. | 2 | | B00347 | = G | | | 150-199 | | |
| B-Q | | | | | 0-0 | 30-71-21 | B00373 | = P | | | SP03372 | | 9 | | 150-199 | | |
| B-R | | | | | 0-0 | 30-71-21 | B00373 | = G | | | SP03978 | | 9 | | 150-199 | | |
| B-Y | | | | | 0-0 | 30-71-22 | SP03932 | | | 9 | B00412 | = P | | | 275-299 | | |
| B-Z | | | | | 0-0 | 30-71-21 | B00133 | = G | | | GD04386 | A.. | E | | ALL | | |
| C-E | | | | | 0-0 | 30-71-22 | SP02146 | | | 9 | B00159 | = P | | | ALL | | |
| C-F | | | | | 0-0 | 30-71-22 | B00159 | = G | | | SP02148 | | 9 | | ALL | | |
| C-N | | | | | 0-0 | 30-71-22 | SP03934 | | | 9 | B00414 | = P | | | 275-299 | | |
| C-O | | | | | 0-0 | 30-71-22 | SP03936 | | | 9 | B00411 | = P | | | 275-299 | | |
| C-P | | | | | 0-0 | 30-71-22 | SP03938 | | | 9 | B00413 | = P | | | 275-299 | | |
| C-Q | | | | | 0-0 | 30-71-22 | B00412 | = G | | | SP03940 | | 9 | | 275-299 | | |
| C-R | | | | | 0-0 | 30-71-22 | B00414 | = G | | | SP03942 | | 9 | | 275-299 | | |
| C-S | | | | | 0-0 | 30-71-22 | B00411 | = G | | | SP03944 | | 9 | | 275-299 | | |
| C-T | | | | | 0-0 | 30-71-22 | B00413 | = G | | | SP03946 | | 9 | | 275-299 | | |
| C-U | | | | | 0-0 | 30-71-21 | B00415 | = P | | | SP03974 | | 9 | | 050-099 | | |
| C-U | | | | | 0-0 | 30-71-21 | SP03974 | | | 9 | B00415 | = P | | | 155-199 | | |
| C-V | | | | | 0-0 | 30-71-21 | B00415 | = G | | | GD01056 | A.. | 2 | | 050-099 | | |
| C-V | | | | | 0-0 | 30-71-21 | GD01056 | A.. | 2 | | B00415 | = G | | | 155-199 | | |
| D-A | | | | | 0-0 | 30-71-21 | SP00382 | | | 9 | B00107 | = P | | | ALL | | |
| D-B | | | | | 0-0 | 30-71-21 | GD04384 | A.. | E | | B00107 | = G | | | ALL | | |
| D-E | | | | | 0-0 | 30-71-22 | SP02150 | | | 9 | B00160 | = P | | | 050-099 | | |
| D-E | | | | | 0-0 | 30-71-22 | B00160 | = P | | | SP02150 | | 9 | | 150-199, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | | | | To | | | | |
|--------------|-----------------|---|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1258 | 286T1258 | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | |
| D-F | | 0-0 30-71-22 | B00160 | =G | | | SP02152 | | 9 | | ALL |
| D-I | | 0-0 30-71-22 | B00421 | =P | | | SP04000 | | 9 | | 050-099 |
| D-J | | 0-0 30-71-22 | B00421 | =G | | | GD04408 | A.. | E | | 050-099 |
| D-K | | 0-0 30-71-22 | B00422 | =P | | | SP04002 | | 9 | | 050-099 |
| D-L | | 0-0 30-71-22 | B00422 | =G | | | SP05080 | | 9 | | 050-099 |
| D-M | | 0-0 30-71-22 | B00423 | =P | | | SP03994 | | 9 | | 050-099 |
| D-N | | 0-0 30-71-22 | B00423 | =G | | | GD04412 | A.. | E | | 050-099 |
| D-O | | 0-0 30-71-22 | B00424 | =P | | | SP03998 | | 9 | | 050-099 |
| D-P | | 0-0 30-71-22 | B00424 | =G | | | GD04412 | A.. | E | | 050-099 |
| D-R | | 0-0 30-71-24 | B00132 | =P | | | SP04006 | | 9 | | 050-099 |
| D-R | | 0-0 30-71-23 | SP04006 | | 9 | | B00425 | =P | | | 277-299 |
| D-S | | 0-0 30-71-24 | B00132 | =G | | | SP04008 | | 9 | | 050-099 |
| D-S | | 0-0 30-71-23 | B00425 | =G | | | SP04008 | | 9 | | 277-299 |
| E-A | | 0-0 30-71-21 | SP00386 | | 9 | | B00120 | =P | | | ALL |
| E-B | | 0-0 30-71-21 | GD01064 | A.. | E | | B00120 | =G | | | 050-099 |
| E-B | | 0-0 30-71-21 | GD05420 | A.. | E | | B00120 | =G | | | 150-199, 275-299 |
| F-A | | 0-0 30-71-21 | SP00390 | | 9 | | B00119 | =P | | | ALL |
| F-B | | 0-0 30-71-21 | GD01064 | A.. | E | | B00119 | =G | | | ALL |
| F-E | | 0-0 30-71-22 | B00164 | =P | | | SP02166 | | 9 | | 050-099, 275-299 |
| F-F | | 0-0 30-71-22 | B00164 | =G | | | SP02168 | | 9 | | 050-099, 275-299 |
| G-A | | 0-0 30-71-21 | SP00394 | | 9 | | B00091 | =P | | | ALL |
| G-B | | 0-0 30-71-21 | GD04386 | A.. | E | | B00091 | =G | | | ALL |
| G-C | | 0-0 30-71-21 | SP03240 | | 9 | | B00260 | =P | | | 150-199 |
| G-D | | 0-0 30-71-21 | B00260 | =G | | | SP03246 | | 9 | | 150-199 |
| G-E | | 0-0 30-71-22 | B00161 | =P | | | SP02170 | | 9 | | 150-199 |
| G-F | | 0-0 30-71-22 | B00161 | =G | | | SP02172 | | 9 | | 150-199 |
| H-A | | 0-0 30-71-22 | SP00400 | | 9 | | B00108 | =P | | | ALL |
| H-B | | 0-0 30-71-22 | GD04376 | A.. | E | | B00108 | =G | | | ALL |
| H-C | | 0-0 30-71-21 | SP03242 | | 9 | | B00264 | =P | | | 150-199, 275-299 |
| H-D | | 0-0 30-71-21 | B00264 | =G | | | GD05420 | A.. | E | | 150-199, 275-299 |
| I-A | | 0-0 30-71-22 | SP00402 | | 9 | | B00096 | =P | | | ALL |
| I-B | | 0-0 30-71-22 | GD04376 | A.. | E | | B00096 | =G | | | ALL |
| I-C | | 0-0 30-71-21 | B00270 | =P | | | SP03250 | | 9 | | 050-099 |
| I-C | | 0-0 30-71-21 | SP03250 | | 9 | | B00270 | =P | | | 150-199 |
| I-D | | 0-0 30-71-21 | B00270 | =G | | | SP03252 | | 9 | | 050-099, 150-199 |
| J-A | | 0-0 30-71-22 | SP00406 | | 9 | | B00092 | =P | | | ALL |
| J-B | | 0-0 30-71-22 | GD00432 | A.. | 2 | | B00092 | =G | | | ALL |
| J-C | | 0-0 30-71-21 | B00269 | =P | | | SP03254 | | 9 | | ALL |
| J-D | | 0-0 30-71-21 | B00269 | =G | | | SP03256 | | 9 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 17

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | Term | Type | Splice | To | Term | Type | Splice | Effectivity |
|--------------|-----------------|---|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip | | | | Equip | | | | |
| W1258 | 286T1258 | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | |
| K-C | | 0-0 30-71-21 | B00366 | =P | | | SP03646 | | 9 | | 050-099, 150-199 |
| K-D | | 0-0 30-71-21 | B00366 | =G | | | SP03956 | | 9 | | 050-099, 150-199 |
| L-A | | 0-0 30-71-21 | SP00618 | | 9 | | B00115 | =P | | | 050-099 |
| L-A | | 0-0 30-71-22 | B00115 | =P | | | SP00618 | | 9 | | 275-299 |
| L-B | | 0-0 30-71-21 | B00115 | =G | | | GD04624 | A.. | E | | 050-099 |
| L-B | | 0-0 30-71-22 | B00115 | =G | | | SP00414 | | 9 | | 275-299 |
| L-C | | 0-0 30-71-21 | B00365 | =P | | | SP03648 | | 9 | | 050-099, 150-199 |
| L-D | | 0-0 30-71-21 | B00365 | =G | | | SP03958 | | 9 | | 050-099, 150-199 |
| L-G | | 0-0 30-71-22 | B00205 | =P | | | SP02458 | | 9 | | 050-099 |
| L-H | | 0-0 30-71-22 | B00205 | =G | | | GD04406 | A.. | E | | 050-099 |
| M-A | | 0-0 30-71-22 | SP00620 | | 9 | | B00116 | =P | | | 275-299 |
| M-B | | 0-0 30-71-22 | B00116 | =G | | | SP00418 | | 9 | | 275-299 |
| M-C | | 0-0 30-71-21 | B00364 | =P | | | SP03650 | | 9 | | 050-099, 150-199 |
| M-D | | 0-0 30-71-21 | B00364 | =G | | | SP03960 | | 9 | | 050-099, 150-199 |
| N-A | | 0-0 30-71-22 | SP00416 | | 9 | | B00114 | =P | | | 050-099 |
| N-B | | 0-0 30-71-22 | GD04404 | | A.. | E | B00114 | =G | | | 050-099 |
| O-A | | 0-0 30-71-21 | B00113 | =P | | | SP00422 | | 9 | | 050-099 |
| O-B | | 0-0 30-71-21 | B00113 | =G | | | GD01064 | A.. | E | | 050-099 |
| P-A | | 0-0 30-71-21 | B00111 | =P | | | SP00426 | | 9 | | 050-099 |
| P-B | | 0-0 30-71-21 | B00111 | =G | | | GD01064 | A.. | E | | 050-099 |
| P-G | | 0-0 30-71-23 | B00095 | =P | | | SP00438 | | 9 | | 050-099 |
| P-G | | 0-0 30-71-24 | SP00438 | | 9 | | B00095 | =P | | | 150-199 |
| P-H | | 0-0 30-71-23 | B00095 | =G | | | GD04376 | A.. | E | | 050-099 |
| P-H | | 0-0 30-71-24 | B00095 | =G | | | GD04376 | A.. | E | | 150-199 |
| Q-A | | 0-0 30-71-21 | B00109 | =P | | | SP00430 | | 9 | | ALL |
| Q-B | | 0-0 30-71-21 | B00109 | =G | | | SP00432 | | 9 | | ALL |
| R-A | | 0-0 30-71-21 | B00103 | =P | | | SP00434 | | 9 | | 050-099 |
| R-B | | 0-0 30-71-21 | B00103 | =G | | | GD01092 | A.. | E | | 050-099 |
| R-C | | 0-0 30-71-21 | B00363 | =P | | | SP03652 | | 9 | | 050-099, 150-199 |
| R-D | | 0-0 30-71-21 | B00363 | =G | | | SP03962 | | 9 | | 050-099, 150-199 |
| R-G | | 0-0 30-71-22 | B00367 | =P | | | SP02166 | | 9 | | 150-199 |
| R-H | | 0-0 30-71-22 | B00367 | =G | | | SP02168 | | 9 | | 150-199 |
| S-C | | 0-0 30-71-21 | B00374 | =P | | | SP03654 | | 9 | | 150-199 |
| S-D | | 0-0 30-71-21 | B00374 | =G | | | SP03973 | | 9 | | 150-199 |
| S-G | | 0-0 30-71-22 | B00371 | =P | | | SP02456 | | 9 | | 150-199 |
| S-H | | 0-0 30-71-22 | B00371 | =G | | | SP02476 | | 9 | | 150-199 |
| T-C | | 0-0 30-71-22 | SP01652 | | 9 | | B00131 | =P | | | 050-099 |
| T-D | | 0-0 30-71-22 | B00131 | =G | | | SP01654 | | 9 | | 050-099 |
| T-G | | 0-0 30-71-22 | B00375 | =P | | | SP03642 | | 9 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1250

Page 18

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|------|--------|---------|-------------|-----|---|--|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W1258 | 286T1258 | | | WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | | | | | | |
| T-H | | | | | 0-0 | 30-71-22 | B00375 | | = G | | | | | | SP03644 | | 9 | | | 150-199 |
| U-C | | | | | 0-0 | 30-71-21 | SP01640 | | | | | | | 9 | B00097 | | = P | | | ALL |
| U-D | | | | | 0-0 | 30-71-21 | B00097 | | = G | | | | | | GD01056 | | A.. | 2 | | ALL |
| U-G | | | | | 0-0 | 30-71-22 | B00372 | | = P | | | | | | SP03996 | | | 9 | | 050-099 |
| U-G | | | | | 0-0 | 30-71-22 | B00372 | | = P | | | | | | SP00416 | | | 9 | | 150-199 |
| U-H | | | | | 0-0 | 30-71-22 | B00372 | | = G | | | | | | SP00420 | | | 9 | | 050-099 |
| U-H | | | | | 0-0 | 30-71-22 | SP00420 | | | | | | 9 | B00372 | | = G | | | | 150-199 |
| V-G | | | | | 0-0 | 30-71-22 | B00368 | | = P | | | | | | SP02158 | | | 9 | | 150-199 |
| V-H | | | | | 0-0 | 30-71-22 | B00368 | | = G | | | | | | GD04402 | | A.. | E | | 150-199 |
| W-G | | | | | 0-0 | 30-71-22 | B00369 | | = P | | | | | | SP02162 | | | 9 | | 150-199 |
| W-H | | | | | 0-0 | 30-71-22 | B00369 | | = G | | | | | | SP02164 | | | 9 | | 150-199 |
| X-C | | | | | 0-0 | 30-71-11 | B00041 | | = P | | | | | | SP00366 | | | 9 | | ALL |
| X-D | | | | | 0-0 | 30-71-11 | B00041 | | = G | | | | | | GD04380 | | A.. | E | | 050-099 |
| X-D | | | | | 0-0 | 30-71-11 | B00041 | | = G | | | | | | SP00368 | | | 9 | | 150-199, 275-299 |
| X-G | | | | | 0-0 | 30-71-22 | B00370 | | = P | | | | | | SP02458 | | | 9 | | 150-199 |
| X-H | | | | | 0-0 | 30-71-22 | B00370 | | = G | | | | | | SP04010 | | | 9 | | 150-199 |
| Y-A | | | | | 0-0 | 30-71-23 | B00104 | | = P | | | | | | SP00456 | | | 9 | | 050-099 |
| Y-A | | | | | 0-0 | 30-71-24 | SP00456 | | | | | | 9 | B00104 | | = P | | | | 150-199 |
| Y-B | | | | | 0-0 | 30-71-23 | B00104 | | = G | | | | | | SP00458 | | | 9 | | 050-099 |
| Y-B | | | | | 0-0 | 30-71-24 | SP00458 | | | | | | 9 | B00104 | | = G | | | | 150-199 |
| Y-C | | | | | 0-0 | 30-71-21 | SP01644 | | | | | | 9 | B00090 | | = P | | | | ALL |
| Y-D | | | | | 0-0 | 30-71-21 | B00090 | | = G | | | | | | GD01056 | | A.. | 2 | | ALL |
| Z-A | | | | | 0-0 | 30-71-23 | SP00624 | | | | | | 9 | B00132 | | = P | | | | 150-199 |
| Z-B | | | | | 0-0 | 30-71-23 | SP00448 | | | | | | 9 | B00132 | | = G | | | | 150-199 |
| Z-E | | | | | 0-0 | 30-71-22 | SP01836 | | | | | | 9 | B00151 | | = P | | | | 050-099, 150-199 |
| Z-F | | | | | 0-0 | 30-71-22 | B00151 | | = G | | | | | | SP02628 | | | 9 | | 050-099 |
| Z-F | | | | | 0-0 | 30-71-22 | B00151 | | = G | | | | | | GD04376 | | A.. | E | | 150-199 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1261 | 286T1261 | | | ELEC SPOILER CONT R2A,SHELF TO W/W DISC | | | | | | | | | | | | |
| 001 | 18 | | PA | 123-0 | 22-21-21 | D05483P | 17 | DK | | D04567P | 15 | DK | | 050-099 | | |
| 001 | 18 | | PA | 145-0 | 22-21-21 | D05483P | 17 | DK | | D04567P | 15 | DK | | 150-199, 275-299 | | |
| 002Y | 22 | | PJ | 123-0 | 27-41-21 | D05483P | 32 | | | D04479P | 8 | | | 050-099 | | |
| 002Y | 22 | | PJ | 145-0 | 27-41-21 | D05483P | 32 | | | D04479P | 8 | | | 150-199, 275-299 | | |
| 003Y | 22 | | PJ | 123-0 | 27-41-21 | D05483P | 33 | | | D04479P | 9 | | | 050-099 | | |
| 003Y | 22 | | PJ | 145-0 | 27-41-21 | D05483P | 33 | | | D04479P | 9 | | | 150-199, 275-299 | | |
| 004 | 22 | | PA | 123-0 | 27-41-21 | D05483P | 34 | | | D04479P | 1 | | | 050-099 | | |
| 004 | 22 | | PA | 145-0 | 27-41-21 | D05483P | 34 | | | D04479P | 1 | | | 150-199, 275-299 | | |
| 005 | 22 | | PA | 123-0 | SPARE | D05483P | 40 | | | D04567P | 13 | | | 050-099 | | |
| 005 | 22 | | PA | 145-0 | SPARE | D05483P | 40 | | | D04567P | 13 | | | 150-199, 275-299 | | |
| 006 | 22 | | PA | 123-0 | SPARE | D05483P | 41 | | | D04479P | 10 | | | 050-099 | | |
| 006 | 22 | | PA | 145-0 | SPARE | D05483P | 41 | | | D04479P | 10 | | | 150-199, 275-299 | | |
| 201B | 20 | | PB IA | 92-0 | 27-61-13 | D05483P | 3 | | | D05233P | 3 | | | 050-099 | | |
| 201B | 20 | | PB IA | 104-0 | 27-61-13 | D05483P | 3 | | | D05233P | 3 | | | 150-199, 275-299 | | |
| 201R | 20 | | PB IA | 0-0 | 27-61-13 | D05483P | 1 | | | D05233P | 1 | | | ALL | | |
| 203B | 20 | | PB IC | 92-0 | 27-61-13 | D05483P | 9 | | | D05233P | 4 | | | 050-099 | | |
| 203B | 20 | | PB IC | 104-0 | 27-61-13 | D05483P | 9 | | | D05233P | 4 | | | 150-199, 275-299 | | |
| 203R | 20 | | PB IC | 0-0 | 27-61-13 | D05483P | 8 | | | D05233P | 2 | | | ALL | | |
| 204B | 20 | | PB ID | 82-0 | 27-61-13 | D05483P | 11 | | | D05243P | 3 | | | 050-099 | | |
| 204B | 20 | | PB ID | 94-0 | 27-61-13 | D05483P | 11 | | | D05243P | 3 | | | 150-199, 275-299 | | |
| 204R | 20 | | PB ID | 0-0 | 27-61-13 | D05483P | 10 | | | D05243P | 1 | | | ALL | | |
| 206B | 20 | | PB IF | 82-0 | 27-61-13 | D05483P | 15 | | | D05243P | 4 | | | 050-099 | | |
| 206B | 20 | | PB IF | 94-0 | 27-61-13 | D05483P | 15 | | | D05243P | 4 | | | 150-199, 275-299 | | |
| 206R | 20 | | PB IF | 0-0 | 27-61-13 | D05483P | 14 | | | D05243P | 2 | | | ALL | | |
| 207B | 22 | | PB IG | 123-0 | 22-21-21 | D05483P | 19 | | | D04567P | 19 | | | 050-099 | | |
| 207B | 22 | | PB IG | 145-0 | 22-21-21 | D05483P | 19 | | | D04567P | 19 | | | 150-199, 275-299 | | |
| 207R | 22 | | PB IG | 0-0 | 22-21-21 | D05483P | 18 | | | D04567P | 18 | | | ALL | | |
| 208B | 22 | | PB IH | 123-0 | 22-21-21 | D05483P | 24 | | | D04567P | 24 | | | 050-099 | | |
| 208B | 22 | | PB IH | 145-0 | 22-21-21 | D05483P | 24 | | | D04567P | 24 | | | 150-199, 275-299 | | |
| 208R | 22 | | PB IH | 0-0 | 22-21-21 | D05483P | 23 | | | D04567P | 23 | | | ALL | | |
| 209B | 22 | | PB II | 123-0 | 27-21-22 | D05483P | 26 | | | D04567P | 7 | | | 050-099 | | |
| 209B | 22 | | PB II | 145-0 | 27-21-22 | D05483P | 26 | | | D04567P | 7 | | | 150-199, 275-299 | | |
| 209R | 22 | | PB II | 0-0 | 27-21-22 | D05483P | 25 | | | D04567P | 6 | | | ALL | | |
| 210B | 22 | | PB IJ | 123-0 | 27-21-22 | D05483P | 31 | | | D04567P | 10 | | | 050-099 | | |
| 210B | 22 | | PB IJ | 145-0 | 27-21-22 | D05483P | 31 | | | D04567P | 10 | | | 150-199, 275-299 | | |
| 210R | 22 | | PB IJ | 0-0 | 27-21-22 | D05483P | 30 | | | D04567P | 9 | | | ALL | | |
| 301B | 20 | | PC MA | 92-0 | 27-61-13 | D05483P | 4 | | | D05233P | 6 | | | 050-099 | | |
| 301B | 20 | | PC MA | 104-0 | 27-61-13 | D05483P | 4 | | | D05233P | 6 | | | 150-199, 275-299 | | |
| 301R | 20 | | PC MA | 0-0 | 27-61-13 | D05483P | 5 | | | D05233P | 5 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W1260

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|--|----|-------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1261 | 286T1261 | ELEC SPOILER CONT R2A,SHELF TO W/W DISC (continued) | | | | | | | | | | | | | |
| 301Y | 20 | PC | MA | 0-0 | 27-61-13 | D05483P | | 7 | | D05233P | | 7 | | ALL | |
| 302B | 20 | PC | MB | 82-0 | 27-61-13 | D05483P | | 6 | | D05243P | | 6 | | 050-099 | |
| 302B | 20 | PC | MB | 94-0 | 27-61-13 | D05483P | | 6 | | D05243P | | 6 | | 150-199, 275-299 | |
| 302R | 20 | PC | MB | 0-0 | 27-61-13 | D05483P | | 12 | | D05243P | | 5 | | ALL | |
| 302Y | 20 | PC | MB | 0-0 | 27-61-13 | D05483P | | 13 | | D05243P | | 7 | | ALL | |
| 303B | 22 | PC | MC | 123-0 | 22-21-21 | D05483P | | 21 | | D04567P | | 21 | | 050-099 | |
| 303B | 22 | PC | MC | 145-0 | 22-21-21 | D05483P | | 21 | | D04567P | | 21 | | 150-199, 275-299 | |
| 303R | 22 | PC | MC | 0-0 | 22-21-21 | D05483P | | 20 | | D04567P | | 20 | | ALL | |
| 303Y | 22 | PC | MC | 0-0 | 22-21-21 | D05483P | | 22 | | D04567P | | 22 | | ALL | |
| 304B | 22 | PC | MD | 123-0 | 27-21-22 | D05483P | | 28 | | D04567P | | 3 | | 050-099 | |
| 304B | 22 | PC | MD | 145-0 | 27-21-22 | D05483P | | 28 | | D04567P | | 3 | | 150-199, 275-299 | |
| 304R | 22 | PC | MD | 0-0 | 27-21-22 | D05483P | | 27 | | D04567P | | 2 | | ALL | |
| 304Y | 22 | PC | MD | 0-0 | 27-21-22 | D05483P | | 29 | | D04567P | | 4 | | ALL | |
| W1262 | 286T1262 | SPAR FUEL SHUTOFF VALVES R WW | | | | | | | | | | | | | |
| 001 | 18 | VF | A | 95-0 | 28-22-21 | SP01748 | | | S | SP01752 | | 9 | | 050-099 | |
| 001 | 18 | VF | A | 105-0 | 28-22-21 | SP01748 | | | S | SP01752 | | 9 | | 150-199, 275-299 | |
| 001Z | | | A | 0-0 | 28-22-21 | SP01748 | | DED | | SP01942 | | 9 | | ALL | |
| 002 | 18 | UA | | 6-0 | 28-22-21 | GD00437 | | S.. | N | SP01942 | | 9 | | ALL | |
| W1263 | 286T1263 | ELEC SPOILER CONT R2C,SHELF TO W/W DISC | | | | | | | | | | | | | |
| 201B | 20 | PB | IA | 108-0 | 27-61-17 | D05485P | | 3 | | D05235P | | 3 | | 050-099 | |
| 201B | 20 | PB | IA | 117-0 | 27-61-17 | D05485P | | 3 | | D05235P | | 3 | | 150-199, 275-299 | |
| 201R | 20 | PB | IA | 0-0 | 27-61-17 | D05485P | | 1 | | D05235P | | 1 | | ALL | |
| 203B | 20 | PB | IC | 108-0 | 27-61-17 | D05485P | | 9 | | D05235P | | 4 | | 050-099 | |
| 203B | 20 | PB | IC | 117-0 | 27-61-17 | D05485P | | 9 | | D05235P | | 4 | | 150-199, 275-299 | |
| 203R | 20 | PB | IC | 0-0 | 27-61-17 | D05485P | | 8 | | D05235P | | 2 | | ALL | |
| 204B | 20 | PB | ID | 97-0 | 27-61-17 | D05485P | | 11 | | D05241P | | 3 | | 050-099 | |
| 204B | 20 | PB | ID | 106-0 | 27-61-17 | D05485P | | 11 | | D05241P | | 3 | | 150-199, 275-299 | |
| 204R | 20 | PB | ID | 0-0 | 27-61-17 | D05485P | | 10 | | D05241P | | 1 | | ALL | |
| 206B | 20 | PB | IF | 97-0 | 27-61-17 | D05485P | | 15 | | D05241P | | 4 | | 050-099 | |
| 206B | 20 | PB | IF | 106-0 | 27-61-17 | D05485P | | 15 | | D05241P | | 4 | | 150-199, 275-299 | |
| 206R | 20 | PB | IF | 0-0 | 27-61-17 | D05485P | | 14 | | D05241P | | 2 | | ALL | |
| 302B | 20 | PC | MB | 108-0 | 27-61-17 | D05485P | | 23 | | D05235P | | 6 | | 050-099 | |
| 302B | 20 | PC | MB | 117-0 | 27-61-17 | D05485P | | 23 | | D05235P | | 6 | | 150-199, 275-299 | |
| 302R | 20 | PC | MB | 0-0 | 27-61-17 | D05485P | | 5 | | D05235P | | 5 | | ALL | |
| 302Y | 20 | PC | MB | 0-0 | 27-61-17 | D05485P | | 7 | | D05235P | | 7 | | ALL | |
| 303B | 20 | PC | MC | 97-0 | 27-61-17 | D05485P | | 24 | | D05241P | | 6 | | 050-099 | |
| 303B | 20 | PC | MC | 106-0 | 27-61-17 | D05485P | | 24 | | D05241P | | 6 | | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W1260

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1263 | 286T1263 | | | ELEC SPOILER CONT R2C,SHELF TO W/W DISC (continued) | | | | | | | | | | | | |
| 303R | 20 | PC | MC | 0-0 | 27-61-17 | D05485P | | | 12 | | | | D05241P | 5 | | ALL |
| 303Y | 20 | PC | MC | 0-0 | 27-61-17 | D05485P | | | 13 | | | | D05241P | 7 | | ALL |
| W1264 | 286T1264 | | | SPAR FUEL SHUTOFF VALVES L WW | | | | | | | | | | | | |
| 001 | 18 | VF | A | 91-0 | 28-22-21 | SP01750 | | | | S | | | SP01754 | 9 | | 050-099 |
| 001 | 18 | VF | A | 103-0 | 28-22-21 | SP01750 | | | | S | | | SP01754 | 9 | | 150-199, 275-299 |
| 001Z | | | A | 0-0 | 28-22-21 | SP01750 | | DED | | | | | SP01946 | 9 | | ALL |
| 002 | 18 | UA | | 2-10 | 28-22-21 | GD00431 | | | S.. | N | | | SP01946 | 9 | | 050-099 |
| 002 | 18 | UA | | 7-0 | 28-22-21 | GD00431 | | | S.. | N | | | SP01946 | 9 | | 150-199, 275-299 |
| W1265 | 286T1265 | | | ELEC SPOILER CONT R2B,SHELF TO W/W DISC | | | | | | | | | | | | |
| 201B | 20 | PB | IA | 91-5 | 27-61-18 | D05487P | | | 3 | | | | D05237P | 3 | | 050-099 |
| 201B | 20 | PB | IA | 102-0 | 27-61-18 | D05487P | | | 3 | | | | D05237P | 3 | | 150-199, 275-299 |
| 201R | 20 | PB | IA | 0-0 | 27-61-18 | D05487P | | | 1 | | | | D05237P | 1 | | ALL |
| 203B | 20 | PB | IC | 91-5 | 27-61-18 | D05487P | | | 9 | | | | D05237P | 4 | | 050-099 |
| 203B | 20 | PB | IC | 102-0 | 27-61-18 | D05487P | | | 9 | | | | D05237P | 4 | | 150-199, 275-299 |
| 203R | 20 | PB | IC | 0-0 | 27-61-18 | D05487P | | | 8 | | | | D05237P | 2 | | ALL |
| 204B | 20 | PB | ID | 82-1 | 27-61-18 | D05487P | | | 11 | | | | D05239P | 3 | | 050-099 |
| 204B | 20 | PB | ID | 92-0 | 27-61-18 | D05487P | | | 11 | | | | D05239P | 3 | | 150-199, 275-299 |
| 204R | 20 | PB | ID | 0-0 | 27-61-18 | D05487P | | | 10 | | | | D05239P | 1 | | ALL |
| 206B | 20 | PB | IF | 82-1 | 27-61-18 | D05487P | | | 15 | | | | D05239P | 4 | | 050-099 |
| 206B | 20 | PB | IF | 92-0 | 27-61-18 | D05487P | | | 15 | | | | D05239P | 4 | | 150-199, 275-299 |
| 206R | 20 | PB | IF | 0-0 | 27-61-18 | D05487P | | | 14 | | | | D05239P | 2 | | ALL |
| 301B | 20 | PC | MA | 91-5 | 27-61-18 | D05487P | | | 4 | | | | D05237P | 6 | | 050-099 |
| 301B | 20 | PC | MA | 102-0 | 27-61-18 | D05487P | | | 4 | | | | D05237P | 6 | | 150-199, 275-299 |
| 301R | 20 | PC | MA | 0-0 | 27-61-18 | D05487P | | | 5 | | | | D05237P | 5 | | ALL |
| 301Y | 20 | PC | MA | 0-0 | 27-61-18 | D05487P | | | 7 | | | | D05237P | 7 | | ALL |
| 302B | 20 | PC | MB | 82-1 | 27-61-18 | D05487P | | | 6 | | | | D05239P | 6 | | 050-099 |
| 302B | 20 | PC | MB | 92-0 | 27-61-18 | D05487P | | | 6 | | | | D05239P | 6 | | 150-199, 275-299 |
| 302R | 20 | PC | MB | 0-0 | 27-61-18 | D05487P | | | 12 | | | | D05239P | 5 | | ALL |
| 302Y | 20 | PC | MB | 0-0 | 27-61-18 | D05487P | | | 13 | | | | D05239P | 7 | | ALL |
| W1266 | 286T1266 | | | PASS. SIGNS JPR BUNDLE (2 FT .5 INCH LONG) | | | | | | | | | | | | |
| 001 | 20 | PA | | 4-0 | 33-24-13 | D00156 | | | 3 | | | | L00405 | NS | C | 050-099, 150-199 |
| 001 | 20 | PA | | 4-0 | 33-24-11 | D00156 | | | 3 | | | | L00405 | NS | C | 275-299 |
| 002 | 20 | PA | | 4-0 | 33-24-13 | D00156 | | | 4 | | | | L00405 | FSB | C | 050-099, 150-199 |
| 002 | 20 | PA | | 4-0 | MULTI | D00156 | | | 4 | | | | L00405 | FSB | C | 275-299 |
| 003 | 20 | PA | | 4-0 | 33-24-13 | D00156 | | | 5 | | | | L00405 | GND | C | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1260

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--------|------|------|--------|--------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1266 | 286T1266 | | | | PASS. SIGNS JPR BUNDLE (2 FT .5 INCH LONG) (continued) | | | | | | | | | | |
| 003 | 20 | | PA | | 4-0 | MULTI | D00156 | | 5 | | L00405 | GND | C | | 275-299 |
| W1268 | 286T1268 | | | | PASS. SPEAKER JPR BUNDLE-SYS 1 (27", 4K TAP, CONN. SIZE 12-12) | | | | | | | | | | |
| 201B | 22 | PB | A | | 4-0 | 23-31-16 | D00158 | | 2 | | B00069 | COM | Z | | 050-099, 150-199 |
| 201B | 22 | PB | A | | 4-0 | 23-31-15 | D00158 | | 2 | | B00069 | COM | Z | | 275-299 |
| 201R | 22 | PB | A | | 0-0 | 23-31-16 | D00158 | | 1 | | B00069 | 4K | Z | | 050-099, 150-199 |
| 201R | 22 | PB | A | | 0-0 | 23-31-15 | D00158 | | 1 | | B00069 | 4K | Z | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1260
Page 4 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1270 | 286T1270 | | | SPEAKER JPR BUNDLE-SYS 2 (27", 4K TAP, CONN. SIZE 12-12) | | | | | | | | | | | | |
| 201B | 22 | PB | A | 4-0 | MULTI | D01862 | | 7 | | | B00069 | COM | Z | | 050-099, 150-199 | |
| 201R | 22 | PB | A | 0-0 | MULTI | D01862 | | 6 | | | B00069 | 4K | Z | | 050-099, 150-199 | |
| W1271 | 286T1271 | | | CAUTION & WARNING,SHELF TO FWD PNL'S | | | | | | | | | | | | |
| 003 | 24 | PK | | 27-0 | 27-32-11 | D04509P | | 1 | | | TB0066X | A012 | BJ | | ALL | |
| 005 | 22 | PA | | 27-0 | 31-51-33 | D04509P | | 3 | | | TB0070X | D010 | BJ | | ALL | |
| 006 | 24 | PK | | 22-0 | SPARE | D04509P | | 15 | | | D05383J | 15 | | | ALL | |
| 007 | 22 | PA | | 39-0 | 34-12-12 | D05383J | | 3 | | | TB0066X | B009 | BJ | | ALL | |
| 009 | 24 | PK | | 39-0 | 34-12-22 | D05383J | | 6 | | | TB0066X | A010 | BJ | | ALL | |
| 011 | 22 | PA | | 39-0 | 34-33-11 | D05383J | | 5 | | | TB0066X | A013 | BJ | | ALL | |
| 012 | 22 | PA | | 39-0 | 34-33-21 | D05383J | | 4 | | | TB0066X | B013 | BJ | | ALL | |
| 013 | 22 | PA | | 39-0 | 34-33-31 | D05383J | | 10 | | | TB0066X | A014 | BJ | | ALL | |
| 017 | 24 | PK | | 22-0 | SPARE | D04509P | | 14 | | | D05383J | 14 | | | ALL | |
| 018 | 24 | PK | | 27-0 | 31-51-42 | D04509P | | 2 | | | TB0066X | B011 | BJ | | ALL | |
| 022 | 24 | PK | | 22-0 | 31-51-33 | D04509P | | 10 | | | D05383J | 18 | | | ALL | |
| 023 | 24 | PK | | 22-0 | 31-51-33 | D04509P | | 9 | | | D05383J | 19 | | | ALL | |
| 024 | 24 | PK | | 27-0 | 27-32-21 | TB0066X | | | B012 | BJ | D04509P | 8 | | | ALL | |
| 026 | 22 | PA | | 22-0 | 31-51-33 | D04509P | | 11 | | | D05383J | 17 | | | ALL | |
| 032 | 24 | PK | | 27-0 | 31-51-41 | TB0066X | | | A011 | BJ | D04509P | 4 | | | ALL | |
| 035 | 22 | PA | | 22-0 | SPARE | D05383J | | 13 | | | D04509P | 13 | | | ALL | |
| 036 | 24 | PK | | 39-0 | 34-46-12 | D05383J | | 21 | | | TB0066X | B010 | BJ | | ALL | |
| 201B | 24 | PL | IA | 22-0 | 27-32-11 | D05383J | | 11 | | | D04509P | 7 | | | ALL | |
| 201R | 24 | PL | IA | 0-0 | 27-32-11 | D05383J | | 8 | | | D04509P | 6 | | | ALL | |
| W1272 | 286T1272 | | | PASS. SPEAKER JPR BUNDLE SYS 1 (50", 4K TAP, CONN. SIZE 12-12) | | | | | | | | | | | | |
| 201B | 22 | PB | A | 6-0 | 23-31-15 | D00160 | | 2 | | | B00069 | COM | Z | | 050-099, 162-199, 280-299 | |
| 201R | 22 | PB | A | 0-0 | 23-31-15 | D00160 | | 1 | | | B00069 | 4K | Z | | 050-099, 162-199, 280-299 | |
| W1274 | 286T1274 | | | FUEL PRESSURE IND,FUEL PUMPS | | | | | | | | | | | | |
| 001 | 22 | PA | | 82-0 | 28-42-12 | D05890P | | 8 | | | D04600J | 5 | | | 050-099 | |
| 001 | 22 | PA | | 92-0 | 28-42-12 | D05890P | | 8 | | | D04600J | 5 | | | 150-199, 275-299 | |
| 002 | 22 | PA | | 82-0 | 28-42-31 | D05890P | | 5 | | | D04600J | 6 | | | 050-099 | |
| 002 | 22 | PA | | 92-0 | 28-42-31 | D05890P | | 5 | | | D04600J | 6 | | | 150-199, 275-299 | |
| 003 | 22 | PA | | 82-0 | 28-42-11 | D05890P | | 6 | | | D04600J | 1 | | | 050-099 | |
| 003 | 22 | PA | | 92-0 | 28-42-11 | D05890P | | 6 | | | D04600J | 1 | | | 150-199, 275-299 | |
| 007 | 14 | PA | | 82-0 | 28-22-11 | D05890P | | 4 | FN | | D04600J | 2 | FO | | 050-099 | |

WIRE LIST

D280T132

91-21-11

Section W1270

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1274 | 286T1274 | | | FUEL PRESSURE IND,FUEL PUMPS (continued) | | | | | | | | | | | |
| 007 | 14 | | PA | | 92-0 | 28-22-11 | D05890P | 4 | FN | | D04600J | 2 | FO | | 150-199, 275-299 |
| 008 | 14 | | PA | | 82-0 | 28-22-11 | D05890P | 7 | FN | | D04600J | 3 | FO | | 050-099 |
| 008 | 14 | | PA | | 92-0 | 28-22-11 | D05890P | 7 | FN | | D04600J | 3 | FO | | 150-199, 275-299 |
| 009 | 14 | | PA | | 82-0 | 28-22-11 | D05890P | 10 | FN | | D04600J | 4 | FO | | 050-099 |
| 009 | 14 | | PA | | 92-0 | 28-22-11 | D05890P | 10 | FN | | D04600J | 4 | FO | | 150-199, 275-299 |
| 010 | 20 | | PA | | 82-0 | SPARE | D05890P | | CAP | Y | D04600J | 7 | | | 050-099 |
| 010 | 20 | | PA | | 92-0 | SPARE | D05890P | | CAP | Y | D04600J | 7 | | | 150-199, 275-299 |
| 100 | 20 | | PQ | E | 82-0 | 28-22-31 | D04600J | 9 | | | D05890P | 1 | | | ALL |
| 100Z | | | | E | 0-0 | 28-22-31 | D04600J | | DED | | D05890P | | DED | | ALL |
| 101 | 20 | | PQ | B | 5-0 | 28-22-31 | D04600J | 10 | | | GD00432 | | D.. | 2 | ALL |
| 101Z | | | | B | 0-0 | 28-22-31 | D04600J | | DED | | GD00432 | | DED | | ALL |
| 102 | 20 | | PQ | C | 82-0 | 28-22-31 | D04600J | 11 | | | D05890P | 2 | | | ALL |
| 102Z | | | | C | 0-0 | 28-22-31 | D04600J | | DED | | D05890P | | DED | | ALL |
| 103 | 20 | | PQ | D | 82-0 | 28-22-31 | D04600J | 12 | | | D05890P | 3 | | | ALL |
| 103Z | | | | D | 0-0 | 28-22-31 | D04600J | | DED | | D05890P | | DED | | ALL |
| W1276 | 286T1276 | | | RIGHT AFT LAV | | | | | | | | | | | |
| 002 | 18 | | PA | | 0-6 | 33-26-11 | D00816 | 6 | | | SM00001 | 9 | | | 275-276 |
| 002 | 18 | | PA | | 0-6 | 33-26-11 | D00816 | 6 | | | SM00001 | | S | | 277-299 |
| 003 | 22 | | PA | | 59-6 | 33-26-11 | D00816 | 15 | | | D05954P | 9 | | | 275-299 |
| 004 | 20 | | PA | | 59-6 | 33-26-11 | D00816 | 17 | | | D05954P | 7 | | | 275-299 |
| 005 | 16 | | PA | | 10-6 | 38-13-11 | D00816 | 2 | | | GD00020 | | A.. | 2 | 275-299 |
| 006 | 20 | | PA | | 10-6 | 33-26-11 | D00816 | 1 | | | GD00020 | | A.. | 2 | 275-299 |
| 007 | 20 | | PA | | 59-6 | 33-26-21 | D00816 | 10 | | | D05954P | 10 | | | 275-299 |
| 008 | 20 | | PA | | 13-9 | 33-26-21 | D00816 | 13 | | | SP01582 | | S | | 275-299 |
| 009 | 20 | | PA | | 59-6 | 33-24-11 | D00816 | 12 | | | D05954P | 12 | | | 275-299 |
| 010 | 16 | | PA | | 59-6 | 38-13-11 | D00816 | 8 | | | D05954P | 4 | | | 275-299 |
| 011 | 22 | | PA | | 14-6 | 33-25-11 | D00816 | 7 | | | B00147 | | HI | C | 275-278 |
| 011 | 22 | | PA | | 16-2 | 33-25-11 | D00816 | 7 | | | B00147 | | HI | C | 280-299 |
| 012 | 22 | | PA | | 59-6 | 33-25-11 | D00816 | 9 | | | D05954P | 8 | | | 275-299 |
| 013 | 22 | | PA | | 6-3 | 33-25-11 | D00816 | 25 | | | SP00576 | | S | | 275-299 |
| 014 | 20 | | PA | | 10-6 | 33-25-11 | D00816 | 26 | | | GD00020 | | D.. | 2 | 275-299 |
| 015 | 18 | | PA | | 59-6 | 38-32-12 | D00816 | 20 | DK | | D05954P | 3 | DL | | 275-276 |
| 015 | 18 | | PA | | 29-8 | 38-32-16 | D00816 | 20 | DK | | SP03988 | 9 | | | 277-299 |
| 016 | 22 | | PA | | 29-8 | 38-32-12 | D00816 | 21 | | | SP01628 | 9 | | | 275-276 |
| 016 | 22 | | PA | | 29-8 | 38-32-16 | D00816 | 21 | | | SP01628 | 9 | | | 277-299 |
| 017 | 20 | | PA | | 10-6 | 38-32-12 | D00816 | 18 | | | GD00020 | | D.. | 2 | 275-276 |
| 017 | 20 | | PA | | 10-6 | 38-32-16 | D00816 | 18 | | | GD00020 | | D.. | 2 | 277-299 |
| 018 | 20 | | PA | | 10-6 | 38-32-12 | D00816 | 19 | | | GD00020 | | S.. | 2 | 275-276 |

WIRE LIST

D280T132

91-21-11

Section W1270

Page 2

Mar 09/2006



| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1276 | 286T1276 | | | RIGHT AFT LAV (continued) | | | | | | | | | | | |
| 018 | 20 | | PA | | 10-6 | 38-32-16 | D00816 | 19 | | | GD00020 | S.. | 2 | | 277-299 |
| 019 | 18 | | PA | | 62-7 | 38-32-16 | D05954P | 3 | DL | | SP03988 | | 9 | | 277-299 |
| 020 | 22 | | PA | | 62-7 | 38-32-12 | D05954P | 1 | | | SP01628 | | 9 | | 275-276 |
| 020 | 22 | | PA | | 62-7 | 38-32-16 | D05954P | 1 | | | SP01628 | | 9 | | 277-299 |
| 021 | 20 | | PA | | 59-6 | 25-42-11 | D05954P | 5 | | | D00816 | 29 | | | 275-299 |
| 043 | 22 | | PA | | 59-6 | 33-26-11 | SM00001 | | 9 | | D05954P | 2 | | | 275-276 |
| 043 | 22 | | PA | | 59-6 | 33-26-11 | SM00001 | | S | | D05954P | 2 | | | 277-299 |
| 201B | 22 | | PB | A | 13-9 | 23-31-14 | D00816 | 5 | | | SP01698 | | S | | 275-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-14 | D00816 | 16 | | | SP01696 | | S | | 275-299 |
| W1278 | 286T1278 | | | PASS. SIGNS JPR BUNDLE (2 FT 10.5 INCH LONG) | | | | | | | | | | | |
| 001 | 22 | | PA | | 4-0 | 33-24-14 | D00162 | 3 | | | L00405 | NS | C | | ALL |
| 002 | 22 | | PA | | 4-0 | 33-24-14 | D00162 | 4 | | | L00405 | FSB | C | | ALL |
| 003 | 22 | | PA | | 4-0 | 33-24-14 | D00162 | 5 | | | L00405 | GND | C | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286T1280 | | | CENTER PSU | | | | | | | | | | | |
| 001 | 18 | | PA | | 3-0 | 33-24-13 | D05972J | | 1 | DL | SM00001 | | | S | 050-099 |
| 001 | 18 | | PA | | 3-0 | 33-24-13 | D05972J | | 1 | DL | SM00003 | | | S | 150-199 |
| 001 | 18 | | PA | | 4-0 | 33-24-13 | D08184J | | 1 | DL | SM00003 | | | S | 275 |
| 001 | 18 | | PA | | 4-0 | 33-24-13 | D08184J | | 2 | DL | SM00003 | | | S | 276-278 |
| 002 | 18 | | PA | | 3-0 | 33-24-13 | D05972J | | 2 | DL | SM00002 | | | S | 050-099 |
| 002 | 18 | | PA | | 3-0 | 33-24-13 | D05972J | | 2 | DL | SM00004 | | | S | 150-199 |
| 002 | 18 | | PA | | 4-0 | 33-24-13 | D08184J | | 2 | DL | SM00004 | | | S | 275 |
| 002 | 18 | | PA | | 4-0 | 33-24-13 | D08184J | | 1 | DL | SM00004 | | | S | 276-278 |
| 003 | 18 | | PA | | 7-0 | 33-24-13 | SM00001 | | | S | SM00003 | | | S | 050-099 |
| 003 | 20 | | PA | | 4-0 | 33-24-13 | D03278 | | 4 | | SM00003 | | | S | 150-199 |
| 003 | 20 | | PA | | 4-0 | 33-24-13 | D02056 | | 3 | | SM00003 | | | S | 275-278 |
| 004 | 18 | | PA | | 7-0 | 33-24-13 | SM00002 | | | S | SM00004 | | | S | 050-099 |
| 004 | 20 | | PA | | 4-0 | 33-24-13 | D03278 | | 3 | | SM00004 | | | S | 150-199 |
| 004 | 20 | | PA | | 4-0 | 33-24-13 | D02056 | | 4 | | SM00004 | | | S | 275-278 |
| 005 | 18 | | PA | | 7-0 | 33-24-13 | SM00003 | | | S | SM00005 | | | S | 050-099 |
| 005 | 20 | | PA | | 8-0 | 33-24-13 | D03278 | | 5 | | GD05080 | A.. | 2 | | 150-199 |
| 005 | 20 | | PA | | 8-0 | 33-24-13 | D02056 | | 5 | | GD04198 | A.. | 2 | | 275-278 |
| 006 | 18 | | PA | | 7-0 | 33-24-13 | SM00004 | | | S | SM00006 | | | S | 050-099 |
| 006 | 18 | | PA | | 5-0 | 33-24-13 | SM00004 | | | S | SM00012 | | | S | 150-199 |
| 006 | 18 | | PA | | 5-0 | 33-24-13 | SM00070 | | | S | SM00004 | | | S | 275-278 |
| 007 | 18 | | PA | | 10-0 | 33-24-13 | SM00005 | | | S | SM00011 | | | S | 050-099 |
| 007 | 18 | | PA | | 5-0 | 33-24-13 | SM00003 | | | S | SM00011 | | | S | 150-199 |
| 007 | 18 | | PA | | 5-0 | 33-24-13 | SM00071 | | | S | SM00003 | | | S | 275-278 |
| 008 | 18 | | PA | | 10-0 | 33-24-13 | SM00006 | | | S | SM00012 | | | S | 050-099 |
| 008 | 20 | | PA | | 5-0 | 33-24-13 | D02058 | | 3 | | SM00073 | | | S | 150-199 |
| 009 | 18 | | PA | | 6-0 | 33-24-13 | SM00011 | | | S | D05976P | | 1 | DK | 050-099 |
| 009 | 20 | | PA | | 4-0 | 33-24-13 | D02058 | | 4 | | SM00072 | | | S | 150-199 |
| 010 | 18 | | PA | | 5-0 | 33-24-13 | SM00012 | | | S | D05976P | | 2 | DK | 050-099 |
| 010 | 20 | | PA | | 5-0 | 33-24-13 | D02058 | | 5 | | GD04198 | A.. | 2 | | 150-199 |
| 011 | 20 | | PA | | 3-0 | 33-24-13 | D03294 | | 3 | | SM00081 | | | S | 150-199 |
| 012 | 20 | | PA | | 6-0 | 33-24-13 | D03294 | | 5 | | GD01748 | A.. | 2 | | 150-199 |
| 013 | 20 | | PA | | 3-0 | 33-24-13 | D03294 | | 4 | | SM00080 | | | S | 150-199 |
| 013 | 18 | | PA | | 16-0 | 33-24-13 | SM00070 | | | S | SM00074 | | | S | 275-278 |
| 014 | 18 | | PA | | 5-0 | 33-24-13 | SM00006 | | | S | SM00010 | | | S | 150-199 |
| 014 | 18 | | PA | | 6-0 | 33-24-13 | SM00071 | | | S | SM00075 | | | S | 275-278 |
| 015 | 20 | | PA | | 5-0 | 33-24-13 | D08178 | | 5 | | GD00960 | A.. | 2 | | 150-199 |
| 016 | 20 | | PA | | 3-0 | 33-24-13 | D08178 | | 3 | | SM00005 | | | S | 150-199 |
| 017 | 20 | | PA | | 3-0 | 33-24-13 | D08178 | | 4 | | SM00006 | | | S | 150-199 |
| 018 | 20 | | PA | | 3-0 | 33-24-13 | D03286 | | 3 | | SM00073 | | | S | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1280

Page 1

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1280 | 286T1280 | | | CENTER PSU (continued) | | | | | | | | | | | | | |
| 019 | 20 | | PA | 3-0 | 33-24-13 | D03286 | | 4 | | | | | SM00072 | | S | | 150-199 |
| 020 | 20 | | PA | 4-0 | 33-24-13 | D03286 | | 5 | | | | | GD04198 | A.. | 2 | | 150-199 |
| 021 | 18 | | PA | 7-0 | 33-24-13 | SM00009 | | | S | | | | SM00073 | | S | | 150-199 |
| 021 | 18 | | PA | 8-0 | 33-24-13 | SM00077 | | | S | | | | SM00075 | | S | | 275-278 |
| 022 | 18 | | PA | 6-0 | 33-24-13 | SM00010 | | | S | | | | SM00072 | | S | | 150-199 |
| 022 | 18 | | PA | 7-0 | 33-24-13 | SM00076 | | | S | | | | SM00074 | | S | | 275-278 |
| 023 | 18 | | PA | 8-0 | 33-24-13 | SM00071 | | | S | | | | SM00081 | | S | | 150-199 |
| 023 | 18 | | PA | 7-0 | 33-24-13 | SM00081 | | | S | | | | SM00077 | | S | | 275-278 |
| 024 | 18 | | PA | 7-0 | 33-24-13 | SM00070 | | | S | | | | SM00080 | | S | | 150-199 |
| 024 | 18 | | PA | 7-0 | 33-24-13 | SM00080 | | | S | | | | SM00076 | | S | | 275-278 |
| 025 | 20 | | PA | 2-0 | 33-24-13 | D03290 | | 4 | | | | | SM00076 | | S | | 275-278 |
| 026 | 20 | | PA | 2-0 | 33-24-13 | D03290 | | 3 | | | | | SM00077 | | S | | 275-278 |
| 027 | 20 | | PA | 7-0 | 33-24-13 | D03290 | | 5 | | | | | GD01952 | A.. | 2 | | 275-278 |
| 028 | 18 | | PA | 11-0 | 33-24-13 | SM00071 | | | S | | | | SM00077 | | S | | 150-199 |
| 029 | 18 | | PA | 11-0 | 33-24-13 | SM00070 | | | S | | | | SM00076 | | S | | 150-199 |
| 030 | 20 | | PA | 3-0 | 33-24-13 | D03292 | | 4 | | | | | SM00076 | | S | | 275-278 |
| 031 | 20 | | PA | 3-0 | 33-24-13 | D03292 | | 3 | | | | | SM00077 | | S | | 275-278 |
| 032 | 20 | | PA | 4-0 | 33-24-13 | D03292 | | 5 | | | | | GD01952 | A.. | 2 | | 275-278 |
| 033 | 18 | | PA | 3-0 | 33-24-13 | D05978P | | 2 | DK | | | | SM00081 | | S | | 150-199, 275-278 |
| 034 | 18 | | PA | 3-0 | 33-24-13 | D05978P | | 1 | DK | | | | SM00080 | | S | | 150-199, 275-278 |
| 035 | 20 | | PA | 3-0 | 33-24-13 | D08182 | | 4 | | | | | SM00010 | | S | | 150-199 |
| 035 | 20 | | PA | 3-0 | 33-24-13 | D03294 | | 4 | | | | | SM00080 | | S | | 275-278 |
| 036 | 20 | | PA | 3-0 | 33-24-13 | D08182 | | 3 | | | | | SM00009 | | S | | 150-199 |
| 036 | 20 | | PA | 3-0 | 33-24-13 | D03294 | | 3 | | | | | SM00081 | | S | | 275-278 |
| 037 | 20 | | PA | 5-0 | 33-24-13 | D08182 | | 5 | | | | | GD01940 | A.. | 2 | | 150-199 |
| 037 | 20 | | PA | 5-0 | 33-24-13 | D03294 | | 5 | | | | | GD01952 | A.. | 2 | | 275-278 |
| 041 | 18 | | PA | 5-0 | 33-24-13 | D08184J | | 1 | DL | | | | SM00021 | | S | | 280-299 |
| 042 | 18 | | PA | 5-0 | 33-24-13 | D08184J | | 2 | DL | | | | SM00022 | | S | | 280-299 |
| 043 | 20 | | PA | 2-0 | 33-24-13 | D08180 | | 3 | | | | | SM00005 | | S | | 150-199 |
| 043 | 20 | | PA | 5-0 | 33-24-13 | D03288 | | 3 | | | | | SM00075 | | S | | 275-278 |
| 043 | 18 | | PA | 10-0 | 33-24-13 | SM00021 | | | S | | | | SM00025 | | S | | 280-299 |
| 044 | 20 | | PA | 2-0 | 33-24-13 | D08180 | | 4 | | | | | SM00006 | | S | | 150-199 |
| 044 | 20 | | PA | 10-0 | 33-24-13 | D03288 | | 4 | | | | | SM00074 | | S | | 275-278 |
| 044 | 18 | | PA | 10-0 | 33-24-13 | SM00022 | | | S | | | | SM00026 | | S | | 280-299 |
| 045 | 20 | | PA | 4-0 | 33-24-13 | D08180 | | 5 | | | | | GD04444 | A.. | 2 | | 150-199 |
| 045 | 20 | | PA | 5-0 | 33-24-13 | D03288 | | 5 | | | | | GD01950 | A.. | 2 | | 275-278 |
| 047 | 18 | | PA | 5-0 | 33-24-13 | SM00025 | | | S | | | | SM00031 | | S | | 280-299 |
| 048 | 18 | | PA | 5-0 | 33-24-13 | SM00026 | | | S | | | | SM00032 | | S | | 280-299 |
| 052 | 20 | | PA | 4-0 | 33-24-13 | D03282 | | 3 | | | | | SM00012 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1280

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286T1280 | | | CENTER PSU (continued) | | | | | | | | | | | |
| 053 | 20 | | PA | | 4-0 | 33-24-13 | D03282 | | | | SM00011 | | S | | 150-199 |
| 054 | 20 | | PA | | 3-8 | 33-24-13 | D03282 | | | | GD05080 | A.. | 2 | | 150-199 |
| 057 | 20 | | PA | | 5-0 | 33-24-13 | D13272 | | | | SM00077 | | S | | 150-199 |
| 058 | 20 | | PA | | 5-0 | 33-24-13 | D13272 | | | | SM00076 | | S | | 150-199 |
| 059 | 20 | | PA | | 5-0 | 33-24-13 | D13272 | | | | GD01944 | A.. | 2 | | 150-199 |
| 060 | 20 | | PA | | 6-0 | 33-24-13 | D13278 | | | | SM00071 | | S | | 150-199 |
| 060 | 20 | | PA | | 8-0 | 33-24-13 | D13278 | | | | SM00071 | | S | | 275-278 |
| 061 | 20 | | PA | | 6-0 | 33-24-13 | D13278 | | | | SM00070 | | S | | 150-199 |
| 061 | 20 | | PA | | 7-0 | 33-24-13 | D13278 | | | | SM00070 | | S | | 275-278 |
| 062 | 20 | | PA | | 15-0 | 33-24-13 | D13278 | | | | GD01748 | A.. | 2 | | 150-199 |
| 062 | 20 | | PA | | 7-0 | 33-24-13 | D13278 | | | | GD01950 | A.. | 2 | | 275-278 |
| 063 | 20 | | PA | | 7-0 | 33-24-13 | D10492 | | | | SM00071 | | S | | 275-278 |
| 063 | 18 | | PA | | 5-0 | 33-24-13 | SM00031 | | | S | SM00033 | | S | | 280-299 |
| 064 | 20 | | PA | | 6-0 | 33-24-13 | D10492 | | | 4 | SM00070 | | S | | 275-278 |
| 064 | 18 | | PA | | 5-0 | 33-24-13 | SM00032 | | | S | SM00034 | | S | | 280-299 |
| 065 | 20 | | PA | | 8-0 | 33-24-13 | D10492 | | | 5 | GD01950 | A.. | 2 | | 275-278 |
| 065 | 18 | | PA | | 7-0 | 33-24-13 | SM00033 | | | S | SM00035 | | S | | 280-299 |
| 066 | 18 | | PA | | 16-0 | 33-24-13 | SM00006 | | | S | SM00011 | | S | | 150-199 |
| 066 | 18 | | PA | | 7-0 | 33-24-13 | SM00034 | | | S | SM00036 | | S | | 280-299 |
| 067 | 18 | | PA | | 16-0 | 33-24-13 | SM00005 | | | S | SM00012 | | S | | 150-199 |
| 067 | 18 | | PA | | 4-0 | 33-24-13 | D05978P | | | 1 | SM00035 | | S | | 280-299 |
| 068 | 18 | | PA | | 4-0 | 33-24-13 | D05978P | | | 2 | SM00036 | | S | | 280-299 |
| 074 | 20 | | PA | | 3-0 | 33-24-13 | D03280 | | | 3 | SM00012 | | S | | 150-199 |
| 075 | 20 | | PA | | 3-0 | 33-24-13 | D03280 | | | 4 | SM00011 | | S | | 150-199 |
| 076 | 20 | | PA | | 5-0 | 33-24-13 | D03280 | | | 5 | GD05080 | A.. | 2 | | 150-199 |
| 077 | 20 | | PA | | 2-0 | 33-24-13 | D13496 | | | 3 | SM00077 | | S | | 150-199 |
| 078 | 20 | | PA | | 2-0 | 33-24-13 | D13496 | | | 4 | SM00076 | | S | | 150-199 |
| 079 | 20 | | PA | | 4-0 | 33-24-13 | D13496 | | | 5 | GD00934 | A.. | 2 | | 150-199 |
| 080 | 18 | | PA | | 4-0 | 33-24-13 | SM00076 | | | S | SM00072 | | S | | 150-199 |
| 081 | 18 | | PA | | 3-0 | 33-24-13 | SM00077 | | | S | SM00073 | | S | | 150-199 |
| 082 | 18 | | PA | | 5-0 | 33-24-13 | SM00005 | | | S | SM00009 | | S | | 150-199 |
| 083 | 20 | | PA | | 3-0 | 33-24-13 | D02056 | | | 3 | SM00009 | | S | | 150-199 |
| 084 | 20 | | PA | | 3-0 | 33-24-13 | D02056 | | | 4 | SM00010 | | S | | 150-199 |
| 085 | 20 | | PA | | 7-0 | 33-24-13 | D02056 | | | 5 | GD04198 | A.. | 2 | | 150-199 |
| 103 | 22 | | PA | | 3-0 | 33-24-13 | D03278 | | | 3 | SM00002 | | S | | 050-099 |
| 104 | 22 | | PA | | 3-0 | 33-24-13 | D03278 | | | 4 | SM00001 | | S | | 050-099 |
| 105 | 20 | | PA | | 8-0 | 33-24-13 | D03278 | | | 5 | GD00960 | A.. | 2 | | 050-099 |
| 113 | 22 | | PA | | 4-0 | 33-24-13 | D03280 | | | 3 | SM00002 | | S | | 050-099 |
| 114 | 22 | | PA | | 4-0 | 33-24-13 | D03280 | | | 4 | SM00001 | | S | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W1280
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------|------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1280 | 286T1280 | | | CENTER PSU (continued) | | | | | | | | | | | | | |
| 115 | 20 | | PA | | 6-0 | 33-24-13 | D03280 | | 5 | | | | GD00960 | A.. | 2 | | 050-099 |
| 123 | 22 | | PA | | 3-0 | 33-24-13 | D03282 | | 3 | | | | SM00004 | | S | | 050-099 |
| 124 | 22 | | PA | | 3-0 | 33-24-13 | D03282 | | 4 | | | | SM00003 | | S | | 050-099 |
| 125 | 20 | | PA | | 6-0 | 33-24-13 | D03282 | | 5 | | | | GD00960 | A.. | 2 | | 050-099 |
| 133 | 22 | | PA | | 4-0 | 33-24-13 | D02052 | | 3 | | | | SM00004 | | S | | 050-099 |
| 134 | 22 | | PA | | 4-0 | 33-24-13 | D02052 | | 4 | | | | SM00003 | | S | | 050-099 |
| 135 | 20 | | PA | | 5-0 | 33-24-13 | D02052 | | 5 | | | | GD04444 | A.. | 2 | | 050-099 |
| 143 | 22 | | PA | | 3-0 | 33-24-13 | D02054 | | 3 | | | | SM00006 | | S | | 050-099 |
| 144 | 22 | | PA | | 3-0 | 33-24-13 | D02054 | | 4 | | | | SM00005 | | S | | 050-099 |
| 145 | 20 | | PA | | 6-0 | 33-24-13 | D02054 | | 5 | | | | GD01940 | A.. | 2 | | 050-099 |
| 193 | 22 | | PA | | 4-0 | 33-24-13 | D10492 | | 3 | | | | SM00012 | | S | | 050-099 |
| 194 | 22 | | PA | | 4-0 | 33-24-13 | D10492 | | 4 | | | | SM00011 | | S | | 050-099 |
| 195 | 20 | | PA | | 5-0 | 33-24-13 | D10492 | | 5 | | | | GD00934 | A.. | 2 | | 050-099 |
| 201B | 22 | | PB | IA | 3-0 | 23-31-16 | D05972J | | 3 | | | | SM00102 | | S | | 050-099 |
| 201B | 22 | | PB | A | 2-0 | 23-31-16 | D05972J | | 3 | | | | SM00020 | | S | | 150-199 |
| 201B | 22 | | PB | A | 4-0 | 23-31-16 | D08184J | | 3 | | | | SM00033 | | S | | 275-278 |
| 201R | 22 | | PB | IA | 0-0 | 23-31-16 | D05972J | | 4 | | | | SM00101 | | S | | 050-099 |
| 201R | 22 | | PB | A | 0-0 | 23-31-16 | D05972J | | 4 | | | | SM00019 | | S | | 150-199 |
| 201R | 22 | | PB | A | 0-0 | 23-31-16 | D08184J | | 4 | | | | SM00032 | | S | | 275-278 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-16 | D03278 | | 2 | | | | SM00102 | | S | | 050-099 |
| 202B | 22 | | PB | B | 3-0 | 23-31-16 | D03278 | | 2 | | | | SM00020 | | S | | 150-199 |
| 202B | 22 | | PB | B | 4-0 | 23-31-16 | D02056 | | 2 | | | | SM00033 | | S | | 275-278 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-16 | D03278 | | 1 | | | | SM00101 | | S | | 050-099 |
| 202R | 22 | | PB | B | 0-0 | 23-31-16 | D03278 | | 1 | | | | SM00019 | | S | | 150-199 |
| 202R | 22 | | PB | B | 0-0 | 23-31-16 | D02056 | | 1 | | | | SM00032 | | S | | 275-278 |
| 203B | 22 | | PB | IC | 7-0 | 23-31-16 | SM00102 | | | S | | | SM00104 | | S | | 050-099 |
| 203B | 22 | | PB | C | 4-0 | 23-31-16 | SM00020 | | | S | | | SM00016 | | S | | 150-199 |
| 203B | 22 | | PB | C | 9-0 | 23-31-16 | SM00038 | | | S | | | SM00030 | | S | | 275-278 |
| 203R | 22 | | PB | IC | 0-0 | 23-31-16 | SM00101 | | | S | | | SM00103 | | S | | 050-099 |
| 203R | 22 | | PB | C | 0-0 | 23-31-16 | SM00019 | | | S | | | SM00015 | | S | | 150-199 |
| 203R | 22 | | PB | C | 0-0 | 23-31-16 | SM00037 | | | S | | | SM00029 | | S | | 275-278 |
| 204B | 22 | | PB | ID | 4-0 | 23-31-16 | D03280 | | 2 | | | | SM00102 | | S | | 050-099 |
| 204B | 22 | | PB | D | 3-0 | 23-31-16 | D08178 | | 2 | | | | SM00014 | | S | | 150-199 |
| 204R | 22 | | PB | ID | 0-0 | 23-31-16 | D03280 | | 1 | | | | SM00101 | | S | | 050-099 |
| 204R | 22 | | PB | D | 0-0 | 23-31-16 | D08178 | | 1 | | | | SM00013 | | S | | 150-199 |
| 205B | 22 | | PB | AL | 6-0 | 23-31-16 | D03294 | | 7 | | | | SM00142 | | S | | 150-199 |
| 205R | 22 | | PB | AL | 0-0 | 23-31-16 | D03294 | | 6 | | | | SM00141 | | S | | 150-199 |
| 206B | 22 | | PB | IF | 3-0 | 23-31-16 | D03282 | | 2 | | | | SM00104 | | S | | 050-099 |
| 206R | 22 | | PB | IF | 0-0 | 23-31-16 | D03282 | | 1 | | | | SM00103 | | S | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1280

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286T1280 | | | CENTER PSU (continued) | | | | | | | | | | | |
| 208B | 22 | PB | IH | | 4-0 | 23-31-16 | D02052 | | | | SM00104 | | S | | 050-099 |
| 208B | 22 | PB | J | | 4-0 | 23-31-16 | D13272 | | | | SM00036 | | S | | 150-199 |
| 208R | 22 | PB | IH | | 0-0 | 23-31-16 | D02052 | | | | SM00103 | | S | | 050-099 |
| 208R | 22 | PB | J | | 0-0 | 23-31-16 | D13272 | | | | SM00035 | | S | | 150-199 |
| 209B | 22 | PB | P | | 7-0 | 23-31-16 | D10492 | | | | SM00025 | | S | | 275-278 |
| 209R | 22 | PB | P | | 0-0 | 23-31-16 | D10492 | | | | SM00026 | | S | | 275-278 |
| 210B | 22 | PB | IJ | | 6-0 | 23-31-16 | D02054 | | | | SM00104 | | S | | 050-099 |
| 210B | 22 | PB | KK | | 7-0 | 23-31-16 | D13278 | | | | SM00036 | | S | | 150-199 |
| 210B | 22 | PB | K | | 8-0 | 23-31-16 | D13278 | | | | SM00025 | | S | | 275-278 |
| 210R | 22 | PB | IJ | | 0-0 | 23-31-16 | D02054 | | | | SM00103 | | S | | 050-099 |
| 210R | 22 | PB | KK | | 0-0 | 23-31-16 | D13278 | | | | SM00035 | | S | | 150-199 |
| 210R | 22 | PB | K | | 0-0 | 23-31-16 | D13278 | | | | SM00026 | | S | | 275-278 |
| 212B | 22 | PB | PP | | 4-0 | 23-31-16 | D03282 | | | | SM00016 | | S | | 150-199 |
| 212R | 22 | PB | PP | | 0-0 | 23-31-16 | D03282 | | | | SM00015 | | S | | 150-199 |
| 215B | 22 | PB | P | | 3-0 | 23-31-16 | D03280 | | | | SM00016 | | S | | 150-199 |
| 215R | 22 | PB | P | | 0-0 | 23-31-16 | D03280 | | | | SM00015 | | S | | 150-199 |
| 216B | 22 | PB | GH | | 3-0 | 23-31-16 | D13496 | | | | SM00028 | | S | | 150-199 |
| 216R | 22 | PB | GH | | 0-0 | 23-31-16 | D13496 | | | | SM00027 | | S | | 150-199 |
| 217B | 22 | PB | IQ | | 5-0 | 23-31-16 | D08184J | | | | SM00114 | | S | | 280-299 |
| 217R | 22 | PB | IQ | | 0-0 | 23-31-16 | D08184J | | | | SM00113 | | S | | 280-299 |
| 218B | 22 | PB | GI | | 4-0 | 23-31-16 | SM00028 | | | | SM00036 | | S | | 150-199 |
| 218R | 22 | PB | GI | | 0-0 | 23-31-16 | SM00027 | | | | SM00035 | | S | | 150-199 |
| 219B | 22 | PB | IS | | 11-0 | 23-31-16 | SM00114 | | | | SM00118 | | S | | 280-299 |
| 219R | 22 | PB | IS | | 0-0 | 23-31-16 | SM00113 | | | | SM00117 | | S | | 280-299 |
| 220B | 22 | PB | IT | | 5-0 | 23-31-16 | D10492 | | | | D05976P | | 3 | | 050-099 |
| 220B | 22 | PB | H | | 4-0 | 23-31-16 | D03294 | | | | D05978P | | 3 | | 150-199 |
| 220R | 22 | PB | IT | | 0-0 | 23-31-16 | D10492 | | | | D05976P | | 4 | | 050-099 |
| 220R | 22 | PB | H | | 0-0 | 23-31-16 | D03294 | | | | D05978P | | 4 | | 150-199 |
| 222B | 22 | PB | JS | | 13-0 | 23-31-16 | SM00132 | | | S | SM00142 | | S | | 150-199 |
| 222B | 22 | PB | IV | | 5-0 | 23-31-16 | D02056 | | | 2 | SM00114 | | S | | 280-299 |
| 222R | 22 | PB | JS | | 0-0 | 23-31-16 | SM00131 | | | S | SM00141 | | S | | 150-199 |
| 222R | 22 | PB | IV | | 0-0 | 23-31-16 | D02056 | | | 1 | SM00113 | | S | | 280-299 |
| 223B | 22 | PB | IW | | 4-0 | 23-31-16 | SM00118 | | | S | SM00120 | | S | | 280-299 |
| 223R | 22 | PB | IW | | 0-0 | 23-31-16 | SM00117 | | | S | SM00119 | | S | | 280-299 |
| 224B | 22 | PB | AM | | 3-0 | 23-31-16 | D05978P | | | 5 | SM00142 | | S | | 150-199 |
| 224R | 22 | PB | AM | | 0-0 | 23-31-16 | D05978P | | | 6 | SM00141 | | S | | 150-199 |
| 225B | 22 | PB | N | | 3-0 | 23-31-16 | D08180 | | | 2 | SM00014 | | S | | 150-199 |
| 225B | 22 | PB | N | | 5-0 | 23-31-16 | D03288 | | | 2 | SM00030 | | S | | 275-278 |
| 225R | 22 | PB | N | | 0-0 | 23-31-16 | D08180 | | | 1 | SM00013 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11
 Section W1280
 Page 5
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1280 | 286T1280 | | | CENTER PSU (continued) | | | | | | | | | | | | | |
| 225R | 22 | PB | N | 0-0 | 23-31-16 | D03288 | | 1 | | | | | SM00029 | | S | | 275-278 |
| 227B | 22 | PB | JB | 5-0 | 23-31-16 | SM00120 | | | S | | | | SM00122 | | S | | 280-299 |
| 227R | 22 | PB | JB | 0-0 | 23-31-16 | SM00119 | | | S | | | | SM00121 | | S | | 280-299 |
| 228B | 22 | PB | F | 3-0 | 23-31-16 | D03286 | | 2 | | | | | SM00029 | | S | | 150-199 |
| 228B | 22 | PB | D | 5-0 | 23-31-16 | SM00033 | | | S | | | | SM00025 | | S | | 275-278 |
| 228R | 22 | PB | F | 0-0 | 23-31-16 | D03286 | | 1 | | | | | SM00030 | | S | | 150-199 |
| 228R | 22 | PB | D | 0-0 | 23-31-16 | SM00032 | | | S | | | | SM00026 | | S | | 275-278 |
| 229B | 22 | PB | G | 3-0 | 23-31-16 | D02056 | | 2 | | | | | SM00025 | | S | | 150-199 |
| 229B | 22 | PB | JD | 7-0 | 23-31-16 | SM00122 | | | S | | | | SM00124 | | S | | 280-299 |
| 229R | 22 | PB | G | 0-0 | 23-31-16 | D02056 | | 1 | | | | | SM00026 | | S | | 150-199 |
| 229R | 22 | PB | JD | 0-0 | 23-31-16 | SM00121 | | | S | | | | SM00123 | | S | | 280-299 |
| 230B | 22 | PB | E | 16-0 | 23-31-16 | SM00016 | | | S | | | | SM00014 | | S | | 150-199 |
| 230B | 22 | PB | E | 6-0 | 23-31-16 | SM00025 | | | S | | | | SM00030 | | S | | 275-278 |
| 230B | 22 | PB | JE | 3-0 | 23-31-16 | D10492 | | 2 | | | | | SM00118 | | S | | 280-299 |
| 230R | 22 | PB | E | 0-0 | 23-31-16 | SM00015 | | | S | | | | SM00013 | | S | | 150-199 |
| 230R | 22 | PB | E | 0-0 | 23-31-16 | SM00026 | | | S | | | | SM00029 | | S | | 275-278 |
| 230R | 22 | PB | JE | 0-0 | 23-31-16 | D10492 | | 1 | | | | | SM00117 | | S | | 280-299 |
| 231B | 22 | PB | GG | 4-0 | 23-31-16 | D02058 | | 2 | | | | | SM00029 | | S | | 150-199 |
| 231B | 22 | PB | JF | 4-0 | 23-31-16 | D05978P | | 3 | | | | | SM00124 | | S | | 280-299 |
| 231R | 22 | PB | GG | 0-0 | 23-31-16 | D02058 | | 1 | | | | | SM00030 | | S | | 150-199 |
| 231R | 22 | PB | JF | 0-0 | 23-31-16 | D05978P | | 4 | | | | | SM00123 | | S | | 280-299 |
| 232B | 22 | PB | H | 3-0 | 23-31-16 | D03290 | | 2 | | | | | SM00038 | | S | | 275-278 |
| 232B | 22 | PB | JG | 5-0 | 23-31-16 | D03286 | | 2 | | | | | SM00120 | | S | | 280-299 |
| 232R | 22 | PB | H | 0-0 | 23-31-16 | D03290 | | 1 | | | | | SM00037 | | S | | 275-278 |
| 232R | 22 | PB | JG | 0-0 | 23-31-16 | D03286 | | 1 | | | | | SM00119 | | S | | 280-299 |
| 233B | 22 | PB | I | 6-0 | 23-31-16 | SM00025 | | | S | | | | SM00029 | | S | | 150-199 |
| 233B | 22 | PB | I | 6-0 | 23-31-16 | SM00042 | | | S | | | | SM00038 | | S | | 275-278 |
| 233R | 22 | PB | I | 0-0 | 23-31-16 | SM00026 | | | S | | | | SM00030 | | S | | 150-199 |
| 233R | 22 | PB | I | 0-0 | 23-31-16 | SM00041 | | | S | | | | SM00037 | | S | | 275-278 |
| 234B | 22 | PB | J | 3-0 | 23-31-16 | D03292 | | 2 | | | | | SM00038 | | S | | 275-278 |
| 234B | 22 | PB | JI | 3-0 | 23-31-16 | D03288 | | 2 | | | | | SM00120 | | S | | 280-299 |
| 234R | 22 | PB | J | 0-0 | 23-31-16 | D03292 | | 1 | | | | | SM00037 | | S | | 275-278 |
| 234R | 22 | PB | JI | 0-0 | 23-31-16 | D03288 | | 1 | | | | | SM00119 | | S | | 280-299 |
| 235B | 22 | PB | K | 5-0 | 23-31-16 | SM00029 | | | S | | | | SM00028 | | S | | 150-199 |
| 235R | 22 | PB | K | 0-0 | 23-31-16 | SM00030 | | | S | | | | SM00027 | | S | | 150-199 |
| 236B | 22 | PB | L | 4-0 | 23-31-16 | D08182 | | 2 | | | | | SM00025 | | S | | 150-199 |
| 236B | 22 | PB | L | 3-0 | 23-31-16 | D03294 | | 2 | | | | | SM00042 | | S | | 275-278 |
| 236B | 22 | PB | JK | 3-0 | 23-31-16 | D03290 | | 2 | | | | | SM00122 | | S | | 280-299 |
| 236R | 22 | PB | L | 0-0 | 23-31-16 | D08182 | | 1 | | | | | SM00026 | | S | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1280

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286T1280 | | | CENTER PSU (continued) | | | | | | | | | | | |
| 236R | 22 | PB | L | | 0-0 | 23-31-16 | D03294 | | 1 | | SM00041 | | S | | 275-278 |
| 236R | 22 | PB | JK | | 0-0 | 23-31-16 | D03290 | | 1 | | SM00121 | | S | | 280-299 |
| 237B | 22 | PB | M | | 6-0 | 23-31-16 | SM00014 | | | S | SM00025 | | S | | 150-199 |
| 237B | 22 | PB | M | | 4-0 | 23-31-16 | SM00042 | | | S | D05978P | 3 | | | 275-278 |
| 237R | 22 | PB | M | | 0-0 | 23-31-16 | SM00013 | | | S | SM00026 | | S | | 150-199 |
| 237R | 22 | PB | M | | 0-0 | 23-31-16 | SM00041 | | | S | D05978P | 4 | | | 275-278 |
| 238B | 22 | PB | XA | | 2-0 | 23-31-16 | D05972J | | 5 | | SM00120 | | S | | 150-199 |
| 238B | 22 | PB | JM | | 4-0 | 23-31-16 | D03292 | | 2 | | SM00122 | | S | | 280-299 |
| 238R | 22 | PB | XA | | 0-0 | 23-31-16 | D05972J | | 6 | | SM00119 | | S | | 150-199 |
| 238R | 22 | PB | JM | | 0-0 | 23-31-16 | D03292 | | 1 | | SM00121 | | S | | 280-299 |
| 239B | 22 | PB | XB | | 3-0 | 23-31-16 | D03278 | | 7 | | SM00120 | | S | | 150-199 |
| 239R | 22 | PB | XB | | 0-0 | 23-31-16 | D03278 | | 6 | | SM00119 | | S | | 150-199 |
| 240B | 22 | PB | XC | | 4-0 | 23-31-16 | SM00116 | | | S | SM00120 | | S | | 150-199 |
| 240B | 22 | PB | JO | | 3-0 | 23-31-16 | D03294 | | 2 | | SM00124 | | S | | 280-299 |
| 240R | 22 | PB | XC | | 0-0 | 23-31-16 | SM00115 | | | S | SM00119 | | S | | 150-199 |
| 240R | 22 | PB | JO | | 0-0 | 23-31-16 | D03294 | | 1 | | SM00123 | | S | | 280-299 |
| 241B | 22 | PB | XD | | 3-0 | 23-31-16 | D03280 | | 7 | | SM00116 | | S | | 150-199 |
| 241R | 22 | PB | XD | | 0-0 | 23-31-16 | D03280 | | 6 | | SM00115 | | S | | 150-199 |
| 242B | 22 | PB | XE | | 16-0 | 23-31-16 | SM00116 | | | S | SM00124 | | S | | 150-199 |
| 242R | 22 | PB | XE | | 0-0 | 23-31-16 | SM00115 | | | S | SM00123 | | S | | 150-199 |
| 243B | 22 | PB | XF | | 4-0 | 23-31-16 | D03282 | | 7 | | SM00116 | | S | | 150-199 |
| 243R | 22 | PB | XF | | 0-0 | 23-31-16 | D03282 | | 6 | | SM00115 | | S | | 150-199 |
| 244B | 22 | PB | XH | | 7-0 | 23-31-16 | SM00124 | | | S | SM00125 | | S | | 150-199 |
| 244R | 22 | PB | XH | | 0-0 | 23-31-16 | SM00123 | | | S | SM00126 | | S | | 150-199 |
| 245B | 22 | PB | XG | | 3-0 | 23-31-16 | D08178 | | 7 | | SM00124 | | S | | 150-199 |
| 245R | 22 | PB | XG | | 0-0 | 23-31-16 | D08178 | | 6 | | SM00123 | | S | | 150-199 |
| 246B | 22 | PB | XI | | 3-0 | 23-31-16 | D08180 | | 7 | | SM00124 | | S | | 150-199 |
| 246R | 22 | PB | XI | | 0-0 | 23-31-16 | D08180 | | 6 | | SM00123 | | S | | 150-199 |
| 247B | 22 | PB | XJ | | 7-0 | 23-31-16 | D08182 | | 7 | | SM00125 | | S | | 150-199 |
| 247R | 22 | PB | XJ | | 0-0 | 23-31-16 | D08182 | | 6 | | SM00126 | | S | | 150-199 |
| 248B | 22 | PB | XK | | 7-0 | 23-31-16 | SM00125 | | | S | SM00129 | | S | | 150-199 |
| 248R | 22 | PB | XK | | 0-0 | 23-31-16 | SM00126 | | | S | SM00130 | | S | | 150-199 |
| 249B | 22 | PB | XL | | 3-0 | 23-31-16 | D02056 | | 7 | | SM00125 | | S | | 150-199 |
| 249R | 22 | PB | XL | | 0-0 | 23-31-16 | D02056 | | 6 | | SM00126 | | S | | 150-199 |
| 250B | 22 | PB | XM | | 5-0 | 23-31-16 | D02058 | | 7 | | SM00129 | | S | | 150-199 |
| 250R | 22 | PB | XM | | 0-0 | 23-31-16 | D02058 | | 6 | | SM00130 | | S | | 150-199 |
| 251B | 22 | PB | KA | | 3-0 | 23-31-16 | D05972J | | 5 | | SM00202 | | S | | 050-099 |
| 251B | 22 | PB | XN | | 3-0 | 23-31-16 | SM00129 | | | S | SM00128 | | S | | 150-199 |
| 251R | 22 | PB | KA | | 0-0 | 23-31-16 | D05972J | | 6 | | SM00201 | | S | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1280

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | | | | | | | |
|--------------|-----------------|----|-------|-------------------------------|------|----------|---------|-------|------|------|--------|-------|------|------|--------|-------------|---------|-----|---|---|---------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | | |
| W1280 | 286T1280 | | | CENTER PSU (continued) | | | | | | | | | | | | | | | | | | |
| 251R | 22 | PB | XN | | 0-0 | 23-31-16 | SM00130 | | | | | | | | S | SM00127 | | | | S | 150-199 | |
| 252B | 22 | PB | KB | | 3-0 | 23-31-16 | D03278 | | 7 | | | | | | | S | SM00202 | | | | S | 050-099 |
| 252B | 22 | PB | XO | | 3-0 | 23-31-16 | D03286 | | 7 | | | | | | | S | SM00129 | | | | S | 150-199 |
| 252R | 22 | PB | KB | | 0-0 | 23-31-16 | D03278 | | 6 | | | | | | | S | SM00201 | | | | S | 050-099 |
| 252R | 22 | PB | XO | | 0-0 | 23-31-16 | D03286 | | 6 | | | | | | | S | SM00130 | | | | S | 150-199 |
| 253B | 22 | PB | KC | | 7-0 | 23-31-16 | SM00202 | | | | | | | | S | SM00204 | | | | S | 050-099 | |
| 253B | 22 | PB | XP | | 3-0 | 23-31-16 | D13496 | | 7 | | | | | | | S | SM00128 | | | | S | 150-199 |
| 253R | 22 | PB | KC | | 0-0 | 23-31-16 | SM00201 | | | | | | | | S | SM00203 | | | | S | 050-099 | |
| 253R | 22 | PB | XP | | 0-0 | 23-31-16 | D13496 | | 6 | | | | | | | S | SM00127 | | | | S | 150-199 |
| 254B | 22 | PB | KD | | 4-0 | 23-31-16 | D03280 | | 7 | | | | | | | S | SM00202 | | | | S | 050-099 |
| 254B | 22 | PB | XQ | | 6-0 | 23-31-16 | SM00132 | | | | | | | | S | SM00128 | | | | S | 150-199 | |
| 254R | 22 | PB | KD | | 0-0 | 23-31-16 | D03280 | | 6 | | | | | | | S | SM00201 | | | | S | 050-099 |
| 254R | 22 | PB | XQ | | 0-0 | 23-31-16 | SM00131 | | | | | | | | S | SM00127 | | | | S | 150-199 | |
| 255B | 22 | PB | KE | | 6-0 | 23-31-16 | SM00204 | | | | | | | | S | SM00206 | | | | S | 050-099 | |
| 255B | 22 | PB | XR | | 3-0 | 23-31-16 | D13272 | | 7 | | | | | | | S | SM00132 | | | | S | 150-199 |
| 255R | 22 | PB | KE | | 0-0 | 23-31-16 | SM00203 | | | | | | | | S | SM00205 | | | | S | 050-099 | |
| 255R | 22 | PB | XR | | 0-0 | 23-31-16 | D13272 | | 6 | | | | | | | S | SM00131 | | | | S | 150-199 |
| 256B | 22 | PB | KF | | 3-0 | 23-31-16 | D03282 | | 7 | | | | | | | S | SM00204 | | | | S | 050-099 |
| 256B | 22 | PB | XT | | 3-0 | 23-31-16 | D13278 | | 7 | | | | | | | S | SM00132 | | | | S | 150-199 |
| 256R | 22 | PB | KF | | 0-0 | 23-31-16 | D03282 | | 6 | | | | | | | S | SM00203 | | | | S | 050-099 |
| 256R | 22 | PB | XT | | 0-0 | 23-31-16 | D13278 | | 6 | | | | | | | S | SM00131 | | | | S | 150-199 |
| 257B | 22 | PB | KG | | 10-0 | 23-31-16 | SM00206 | | | | | | | | S | SM00212 | | | | S | 050-099 | |
| 257R | 22 | PB | KG | | 0-0 | 23-31-16 | SM00205 | | | | | | | | S | SM00211 | | | | S | 050-099 | |
| 258B | 22 | PB | KH | | 4-0 | 23-31-16 | D02052 | | 7 | | | | | | | S | SM00204 | | | | S | 050-099 |
| 258R | 22 | PB | KH | | 0-0 | 23-31-16 | D02052 | | 6 | | | | | | | S | SM00203 | | | | S | 050-099 |
| 260B | 22 | PB | KJ | | 3-0 | 23-31-16 | D02054 | | 7 | | | | | | | S | SM00206 | | | | S | 050-099 |
| 260R | 22 | PB | KJ | | 0-0 | 23-31-16 | D02054 | | 6 | | | | | | | S | SM00205 | | | | S | 050-099 |
| 265B | 22 | PB | KO | | 6-0 | 23-31-16 | D05976P | | 5 | | | | | | | S | SM00212 | | | | S | 050-099 |
| 265R | 22 | PB | KO | | 0-0 | 23-31-16 | D05976P | | 6 | | | | | | | S | SM00211 | | | | S | 050-099 |
| 270B | 22 | PB | KT | | 4-0 | 23-31-16 | D10492 | | 7 | | | | | | | S | SM00212 | | | | S | 050-099 |
| 270R | 22 | PB | KT | | 0-0 | 23-31-16 | D10492 | | 6 | | | | | | | S | SM00211 | | | | S | 050-099 |
| 573 | 20 | PA | | | 4-0 | 33-24-13 | D02056 | | 3 | | | | | | | S | SM00022 | | | | S | 280-299 |
| 574 | 20 | PA | | | 4-0 | 33-24-13 | D02056 | | 4 | | | | | | | S | SM00021 | | | | S | 280-299 |
| 575 | 20 | PA | | | 8-0 | 33-24-13 | D02056 | | 5 | | | | | | | | GD04198 | A.. | 2 | | S | 280-299 |
| 613 | 20 | PA | | | 2-0 | 33-24-13 | D10492 | | 3 | | | | | | | S | SM00026 | | | | S | 280-299 |
| 614 | 20 | PA | | | 2-0 | 33-24-13 | D10492 | | 4 | | | | | | | S | SM00025 | | | | S | 280-299 |
| 615 | 20 | PA | | | 8-0 | 33-24-13 | D10492 | | 5 | | | | | | | | GD01950 | A.. | 2 | | S | 280-299 |
| 643 | 20 | PA | | | 5-0 | 33-24-13 | D03286 | | 3 | | | | | | | S | SM00032 | | | | S | 280-299 |
| 644 | 20 | PA | | | 5-0 | 33-24-13 | D03286 | | 4 | | | | | | | S | SM00031 | | | | S | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1280

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286T1280 | | | CENTER PSU (continued) | | | | | | | | | | | |
| 645 | 20 | | PA | | 7-0 | 33-24-13 | D03286 | | | | GD01950 | A.. | 2 | | 280-299 |
| 653 | 20 | | PA | | 3-0 | 33-24-13 | D03288 | | | | SM00032 | | S | | 280-299 |
| 654 | 20 | | PA | | 3-0 | 33-24-13 | D03288 | | | | SM00031 | | S | | 280-299 |
| 655 | 20 | | PA | | 6-0 | 33-24-13 | D03288 | | | | GD01950 | A.. | 2 | | 280-299 |
| 663 | 20 | | PA | | 3-0 | 33-24-13 | D03290 | | | | SM00034 | | S | | 280-299 |
| 664 | 20 | | PA | | 3-0 | 33-24-13 | D03290 | | | | SM00033 | | S | | 280-299 |
| 665 | 20 | | PA | | 7-0 | 33-24-13 | D03290 | | | | GD01952 | A.. | 2 | | 280-299 |
| 673 | 20 | | PA | | 4-0 | 33-24-13 | D03292 | | | | SM00034 | | S | | 280-299 |
| 674 | 20 | | PA | | 4-0 | 33-24-13 | D03292 | | | | SM00033 | | S | | 280-299 |
| 675 | 20 | | PA | | 5-0 | 33-24-13 | D03292 | | | | GD01952 | A.. | 2 | | 280-299 |
| 683 | 20 | | PA | | 4-0 | 33-24-13 | D03294 | | | | SM00036 | | S | | 280-299 |
| 684 | 20 | | PA | | 4-0 | 33-24-13 | D03294 | | | | SM00035 | | S | | 280-299 |
| 685 | 20 | | PA | | 6-0 | 33-24-13 | D03294 | | | | GD01952 | A.. | 2 | | 280-299 |
| W1281 | 286T1281 | | | ELEC SPOILER CONT L2A,SHELF TO CAPT WHL XDCR AND P10 | | | | | | | | | | | |
| 001 | 20 | | PA | | 3-0 | 27-61-15 | GD00339 | | S.. | E | D00589 | | 6 | | ALL |
| 002 | 20 | | PA | | 3-0 | 27-61-15 | GD00641 | | S.. | 2 | D04131J | | 6 | | ALL |
| 003 | 20 | | PA | | 27-0 | 27-41-11 | D05131P | | | | SM00001 | | 9 | | ALL |
| 004 | 20 | | PA | | 27-0 | 27-41-11 | D05131P | | | | SM00002 | | 9 | | ALL |
| 004Y | 22 | | PJ | | 15-0 | 27-41-11 | SP00029 | | | 9 | SP00437 | | 9 | | 050-099 |
| 005 | 20 | | PA | | 27-0 | 27-41-11 | D05131P | | | 12 | SM00003 | | 9 | | ALL |
| 006 | 20 | | PA | | 3-0 | 27-41-11 | SM00001 | | | 9 | TB0207F | A006 | 2 | | ALL |
| 006Y | 22 | | PJ | | 15-0 | 27-41-11 | SP00011 | | | 9 | SP00405 | | 9 | | 050-099, 275-299 |
| 007 | 20 | | PA | | 3-0 | 27-41-11 | SM00002 | | | 9 | TB0207F | C006 | 2 | | ALL |
| 008 | 20 | | PA | | 3-0 | 27-41-11 | SM00003 | | | 9 | TB0207F | A007 | 2 | | ALL |
| 009 | 20 | | PA | | 7-0 | 27-41-21 | SM00001 | | | 9 | TB0307F | A006 | 2 | | ALL |
| 010 | 20 | | PA | | 7-0 | 27-41-21 | SM00002 | | | 9 | TB0307F | C006 | 2 | | ALL |
| 011 | 20 | | PA | | 7-0 | 27-41-21 | SM00003 | | | 9 | TB0307F | A007 | 2 | | ALL |
| 012Y | 22 | | PJ | | 31-0 | 27-41-11 | D05131P | | | 13 | SP00027 | | 9 | | ALL |
| 013Y | 22 | | PJ | | 31-0 | 27-41-11 | D05131P | | | 14 | SP00009 | | 9 | | ALL |
| 014Y | 22 | | PJ | | 31-0 | 27-41-11 | D05131P | | | 16 | SP00015 | | 9 | | ALL |
| 016Y | 22 | | PJ | | 17-0 | 27-41-11 | SP00009 | | | 9 | SP00567 | | 9 | | 050-099, 278-299 |
| 017Y | 22 | | PJ | | 17-0 | 27-41-11 | SP00011 | | | 9 | SP00565 | | 9 | | 050-099, 278-299 |
| 018Y | 22 | | PJ | | 17-0 | 27-41-11 | SP00027 | | | 9 | SP00571 | | 9 | | 050-099, 278-299 |
| 019Y | 22 | | PJ | | 17-0 | 27-41-11 | SP00015 | | | 9 | SP00569 | | 9 | | 050-099, 278-299 |
| 202B | 22 | | PB | IB | 21-0 | 27-61-15 | D05131P | | | 9 | D00589 | | 1 | | ALL |
| 202R | 22 | | PB | IB | 0-0 | 27-61-15 | D05131P | | | 8 | D00589 | | 2 | | ALL |
| 204B | 22 | | PB | ID | 27-0 | 27-61-15 | D05131P | | | 2 | D04131J | | 2 | | ALL |
| 204R | 22 | | PB | ID | 0-0 | 27-61-15 | D05131P | | | 1 | D04131J | | 1 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1280

Page 9

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-----|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1281 | 286T1281 | | | ELEC SPOILER CONT L2A,SHELF TO CAPT WHL XDCR AND P10 (continued) | | | | | | | | | | | | | |
| 301B | 22 | PC | MA | 21-0 | 27-61-15 | D05131P | | 4 | | | | | D00589 | 4 | | | ALL |
| 301R | 22 | PC | MA | 0-0 | 27-61-15 | D05131P | | 6 | | | | | D00589 | 3 | | | ALL |
| 301Y | 22 | PC | MA | 0-0 | 27-61-15 | D05131P | | 7 | | | | | D00589 | 5 | | | ALL |
| 302B | 22 | PC | MB | 27-0 | 27-61-15 | D05131P | | 15 | | | | | D04131J | 4 | | | ALL |
| 302R | 22 | PC | MB | 0-0 | 27-61-15 | D05131P | | 3 | | | | | D04131J | 3 | | | ALL |
| 302Y | 22 | PC | MB | 0-0 | 27-61-15 | D05131P | | 5 | | | | | D04131J | 5 | | | ALL |
| A-A | | | | 0-0 | 27-41-11 | S00334 | | | COM | E | | | SP00009 | | 9 | | 050-099 |
| A-A | | | | 0-0 | 27-41-11 | S00334 | | | COM | | | | SP00009 | | 9 | | 275-299 |
| A-C | | | | 0-0 | 27-41-11 | S00334 | | | NO | E | | | SP00011 | | 9 | | 050-099 |
| A-C | | | | 0-0 | 27-41-11 | S00334 | | | NO | | | | SP00011 | | 9 | | 275-299 |
| B-A | | | | 0-0 | 27-41-11 | S00335 | | | COM | E | | | SP00027 | | 9 | | 050-099 |
| B-A | | | | 0-0 | 27-41-11 | S00335 | | | COM | | | | SP00027 | | 9 | | 275-299 |
| B-C | | | | 0-0 | 27-41-11 | S00335 | | | NO | E | | | SP00015 | | 9 | | 050-099 |
| B-C | | | | 0-0 | 27-41-11 | S00335 | | | NO | | | | SP00015 | | 9 | | 275-299 |
| C-A | | | | 0-0 | 27-41-11 | S00336 | | | COM | E | | | SP00027 | | 9 | | 050-099 |
| C-C | | | | 0-0 | 27-41-11 | S00336 | | | NO | | | | SP00029 | | 9 | | 050-099 |
| D-A | | | | 0-0 | 27-41-21 | S00838 | | | COM | E | | | SP00575 | | 9 | | 050-099 |
| D-A | | | | 0-0 | 27-41-21 | S00838 | | | COM | | | | SP00575 | | 9 | | 278-299 |
| D-C | | | | 0-0 | 27-41-21 | S00838 | | | NO | E | | | SP00573 | | 9 | | 050-099 |
| D-C | | | | 0-0 | 27-41-21 | S00838 | | | NO | | | | SP00573 | | 9 | | 278-299 |
| E-A | | | | 0-0 | 27-41-21 | S00839 | | | COM | E | | | SP00579 | | 9 | | 050-099 |
| E-A | | | | 0-0 | 27-41-21 | S00839 | | | COM | | | | SP00579 | | 9 | | 278-299 |
| E-C | | | | 0-0 | 27-41-21 | S00839 | | | NO | E | | | SP00577 | | 9 | | 050-099 |
| E-C | | | | 0-0 | 27-41-21 | S00839 | | | NO | | | | SP00577 | | 9 | | 278-299 |
| W1282 | 286T1282 | | | CENTER MID OXYGEN LATCHES STA 729-STA 893 | | | | | | | | | | | | | |
| 001 | 16 | PA | | 6-0 | 35-21-14 | D05994J | | 1 | | | | | SM00001 | | S | | 050-099 |
| 001 | 14 | PA | | 5-0 | 35-21-14 | D05994J | | 1 | FN | | | | SM00001 | | S | | 150-199 |
| 001 | 14 | PA | | 2-0 | 35-21-14 | D08198J | | 1 | FN | | | | SM00001 | | S | | 275-278 |
| 002 | 14 | PA | | 3-0 | 35-21-14 | SM00001 | | | | S | | | SM00002 | | S | | 150-199 |
| 002 | 16 | PA | | 3-0 | 35-21-14 | SM00001 | | | | S | | | SM00002 | | S | | 275-278 |
| 003 | 16 | PA | | 3-0 | 35-21-14 | SM00001 | | | | S | | | SM00003 | | S | | 050-099 |
| 003 | 20 | PA | | 6-0 | 35-21-14 | SM00001 | | | | S | | | D01210 | | 1 | | 150-199 |
| 003 | 20 | PA | | 2-0 | 35-21-14 | D10034 | | 1 | | | | | SM00001 | | S | | 275-278 |
| 004 | 20 | PA | | 5-0 | 35-21-14 | D01210 | | 2 | | | | | GD01930 | | D.. | 2 | 150-199 |
| 004 | 20 | PA | | 7-0 | 35-21-14 | D10034 | | 2 | | | | | GD04198 | | D.. | 2 | 275-278 |
| 005 | 16 | PA | | 5-0 | 35-21-14 | SM00003 | | | | S | | | SM00005 | | S | | 050-099 |
| 005 | 14 | PA | | 5-0 | 35-21-14 | SM00006 | | | | S | | | SM00008 | | S | | 275-278 |
| 006 | 20 | PA | | 3-0 | 35-21-14 | SM00005 | | | | S | | | D10036 | | 1 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1280

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1282 | 286T1282 | | | CENTER MID OXYGEN LATCHES STA 729-STA 893 (continued) | | | | | | | | | | | |
| 006 | 20 | | PA | | 2-0 | 35-21-14 | SM00002 | | | | D00984 | | 1 | | 275-278 |
| 007 | 16 | | PA | | 6-0 | 35-21-14 | SM00005 | | | | SM00007 | | | S | 050-099 |
| 007 | 20 | | PA | | 5-0 | 35-21-14 | D10036 | 2 | | | GD04198 | D.. | 2 | | 150-199 |
| 007 | 20 | | PA | | 7-0 | 35-21-14 | D00984 | 2 | | | GD01940 | D.. | 2 | | 275-278 |
| 008 | 16 | | PA | | 4-0 | 35-21-14 | SM00002 | | | | SM00003 | | | S | 275-278 |
| 009 | 16 | | PA | | 6-0 | 35-21-14 | SM00007 | | | | SM00009 | | | S | 050-099 |
| 009 | 20 | | PA | | 3-0 | 35-21-14 | D10038 | 1 | | | SM00005 | | | S | 150-199 |
| 010 | 20 | | PA | | 4-0 | 35-21-14 | D10038 | 2 | | | GD04198 | D.. | 2 | | 150-199 |
| 011 | 16 | | PA | | 1-0 | 35-21-14 | SM00009 | | | | SM00011 | | | S | 050-099 |
| 012 | 20 | | PA | | 5-0 | 35-21-14 | D00982 | 1 | | | SM00006 | | | S | 150-199 |
| 012 | 20 | | PA | | 8-0 | 35-21-14 | D00982 | 1 | | | SM00003 | | | S | 275-278 |
| 013 | 16 | | PA | | 5-0 | 35-21-14 | SM00011 | | | | D05998P | | 1 | | 050-099 |
| 013 | 20 | | PA | | 4-0 | 35-21-14 | D00982 | 2 | | | GD00934 | D.. | 2 | | 150-199 |
| 013 | 20 | | PA | | 11-0 | 35-21-14 | D00982 | 2 | | | GD01944 | D.. | 2 | | 275-278 |
| 014 | 16 | | PA | | 7-0 | 35-21-14 | SM00003 | | | | SM00006 | | | S | 275-278 |
| 015 | 20 | | PA | | 3-0 | 35-21-14 | D00984 | 1 | | | SM00006 | | | S | 150-199 |
| 016 | 20 | | PA | | 5-0 | 35-21-14 | D00984 | 2 | | | GD00934 | D.. | 2 | | 150-199 |
| 017 | 20 | | PA | | 6-0 | 35-21-14 | D10040 | 1 | | | SM00007 | | | S | 150-199 |
| 017 | 20 | | PA | | 3-0 | 35-21-14 | D10040 | 1 | | | SM00006 | | | S | 275-278 |
| 018 | 20 | | PA | | 3-0 | 35-21-14 | D10040 | 2 | | | GD01944 | D.. | 2 | | 150-199 |
| 018 | 20 | | PA | | 4-0 | 35-21-14 | D10040 | 2 | | | GD01944 | D.. | 2 | | 275-278 |
| 020 | 20 | | PA | | 3-0 | 35-21-14 | SM00003 | | | | D11122 | | 1 | | 150-199 |
| 020 | 20 | | PA | | 8-0 | 35-21-14 | D10646 | 1 | | | SM00003 | | | S | 275-278 |
| 021 | 20 | | PA | | 6-0 | 35-21-14 | D11122 | 2 | | | GD04444 | D.. | 2 | | 150-199 |
| 021 | 20 | | PA | | 4-0 | 35-21-14 | D10646 | 2 | | | GD01944 | D.. | 2 | | 275-278 |
| 023 | 20 | | PA | | 5-0 | 35-21-14 | SM00008 | | | | D10042 | | 1 | | 150-199 |
| 023 | 20 | | PA | | 4-0 | 35-21-14 | SM00008 | | | | D10042 | | 1 | | 275-278 |
| 024 | 20 | | PA | | 7-0 | 35-21-14 | D10042 | 2 | | | GD01950 | D.. | 2 | | 150-199 |
| 024 | 20 | | PA | | 6-0 | 35-21-14 | D10042 | 2 | | | GD01952 | D.. | 2 | | 275-278 |
| 025 | 14 | | PA | | 5-0 | 35-21-14 | SM00008 | | | | SM00009 | | | S | 275-278 |
| 026 | 20 | | PA | | 3-0 | 35-21-14 | SM00004 | | | | D11126 | | 1 | | 150-199 |
| 026 | 20 | | PA | | 2-0 | 35-21-14 | SM00009 | | | | D10044 | | 1 | | 275-278 |
| 027 | 20 | | PA | | 6-0 | 35-21-14 | D11126 | 2 | | | GD01940 | D.. | 2 | | 150-199 |
| 027 | 20 | | PA | | 4-0 | 35-21-14 | D10044 | 2 | | | GD01952 | D.. | 2 | | 275-278 |
| 028 | 20 | | PA | | 5-0 | 35-21-14 | SM00009 | | | | D10046 | | 1 | | 275-278 |
| 029 | 20 | | PA | | 6-0 | 35-21-14 | D10046 | 2 | | | GD01952 | D.. | 2 | | 275-278 |
| 039 | 20 | | PA | | 2-0 | 35-21-14 | D00980 | 1 | | | SM00002 | | | S | 150-199 |
| 040 | 20 | | PA | | 5-0 | 35-21-14 | D00980 | 2 | | | GD05080 | D.. | 2 | | 150-199 |
| 041 | 14 | | PA | | 2-0 | 35-21-14 | D08198J | 1 | FN | | SM00021 | | | S | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1280

Page 11

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1282 | 286T1282 | | | CENTER MID OXYGEN LATCHES STA 729-STA 893 (continued) | | | | | | | | | | | | |
| 043 | 14 | | PA | 5-0 | 35-21-14 | SM00021 | | | | | | S | SM00023 | | S | 280-299 |
| 045 | 14 | | PA | 8-0 | 35-21-14 | SM00023 | | | | | | S | SM00025 | | S | 280-299 |
| 047 | 14 | | PA | 3-0 | 35-21-14 | SM00025 | | | | | | S | SM00031 | | S | 280-299 |
| 051 | 14 | | PA | 13-0 | 35-21-14 | SM00002 | | | | | | S | SM00003 | | S | 150-199 |
| 052 | 14 | | PA | 3-0 | 35-21-14 | SM00003 | | | | | | S | SM00004 | | S | 150-199 |
| 053 | 14 | | PA | 8-0 | 35-21-14 | SM00004 | | | | | | S | SM00005 | | S | 150-199 |
| 054 | 14 | | PA | 8-0 | 35-21-14 | SM00005 | | | | | | S | SM00006 | | S | 150-199 |
| 055 | 14 | | PA | 2-0 | 35-21-14 | SM00006 | | | | | | S | SM00007 | | S | 150-199 |
| 056 | 14 | | PA | 8-0 | 35-21-14 | SM00007 | | | | | | S | SM00008 | | S | 150-199 |
| 057 | 20 | | PA | 7-0 | 35-21-14 | D13548 | | | 1 | | | | SM00007 | | S | 150-199 |
| 058 | 20 | | PA | 4-0 | 35-21-14 | D13548 | | | 2 | | | | GD01950 | D.. | 2 | 150-199 |
| 059 | 20 | | PA | 7-0 | 35-21-14 | D13550 | | | 1 | | | | SM00008 | | S | 150-199 |
| 060 | 20 | | PA | 5-0 | 35-21-14 | D13550 | | | 2 | | | | GD01952 | D.. | 2 | 150-199 |
| 061 | 20 | | PA | 3-0 | 35-21-14 | D00978 | | | 1 | | | | SM00001 | | S | 150-199 |
| 062 | 20 | | PA | 4-0 | 35-21-14 | D00978 | | | 2 | | | | GD05080 | D.. | 2 | 150-199 |
| 063 | 20 | | PA | 6-0 | 35-21-14 | D13608 | | | 1 | | | | SM00002 | | S | 150-199 |
| 063 | 14 | | PA | 7-0 | 35-21-14 | SM00031 | | | | | | S | SM00033 | | S | 280-299 |
| 064 | 20 | | PA | 6-0 | 35-21-14 | D13608 | | | 2 | | | | GD04874 | D.. | 2 | 150-199 |
| 065 | 20 | | PA | 5-0 | 35-21-14 | D10034 | | | 1 | | | | SM00004 | | S | 150-199 |
| 066 | 20 | | PA | 4-0 | 35-21-14 | D10034 | | | 2 | | | | GD01940 | D.. | 2 | 150-199 |
| 067 | 20 | | PA | 3-0 | 35-21-14 | D11124 | | | 1 | | | | SM00003 | | S | 150-199 |
| 068 | 20 | | PA | 3-0 | 35-21-14 | D11124 | | | 2 | | | | GD04444 | D.. | 2 | 150-199 |
| 069 | 20 | | PA | 5-0 | 35-21-14 | D00986 | | | 1 | | | | SM00006 | | S | 275-278 |
| 070 | 20 | | PA | 7-0 | 35-21-14 | D00986 | | | 2 | | | | GD01944 | D.. | 2 | 275-278 |
| 101 | 20 | | PA | 6-0 | 35-21-14 | D01210 | | | 1 | | | | SM00001 | | S | 050-099 |
| 102 | 20 | | PA | 8-0 | 35-21-14 | D01210 | | | 2 | | | | GD00960 | D.. | 2 | 050-099 |
| 111 | 20 | | PA | 4-0 | 35-21-14 | D00978 | | | 1 | | | | SM00001 | | S | 050-099 |
| 112 | 20 | | PA | 6-0 | 35-21-14 | D00978 | | | 2 | | | | GD00960 | D.. | 2 | 050-099 |
| 121 | 20 | | PA | 3-0 | 35-21-14 | D00980 | | | 1 | | | | SM00003 | | S | 050-099 |
| 122 | 20 | | PA | 7-0 | 35-21-14 | D00980 | | | 2 | | | | GD00960 | D.. | 2 | 050-099 |
| 131 | 20 | | PA | 3-0 | 35-21-14 | D01854 | | | 1 | | | | SM00003 | | S | 050-099 |
| 132 | 20 | | PA | 4-0 | 35-21-14 | D01854 | | | 2 | | | | GD04444 | D.. | 2 | 050-099 |
| 141 | 20 | | PA | 2-0 | 35-21-14 | D01856 | | | 1 | | | | SM00005 | | S | 050-099 |
| 142 | 20 | | PA | 6-0 | 35-21-14 | D01856 | | | 2 | | | | GD01940 | D.. | 2 | 050-099 |
| 161 | 20 | | PA | 3-0 | 35-21-14 | D10034 | | | 1 | | | | SM00007 | | S | 050-099 |
| 162 | 20 | | PA | 6-0 | 35-21-14 | D10034 | | | 2 | | | | GD04198 | D.. | 2 | 050-099 |
| 171 | 20 | | PA | 3-0 | 35-21-14 | D10038 | | | 1 | | | | SM00009 | | S | 050-099 |
| 172 | 20 | | PA | 6-0 | 35-21-14 | D10038 | | | 2 | | | | GD04198 | D.. | 2 | 050-099 |
| 191 | 20 | | PA | 4-0 | 35-21-14 | D00984 | | | 1 | | | | SM00011 | | S | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1280

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1282 | 286T1282 | | | CENTER MID OXYGEN LATCHES STA 729-STA 893 (continued) | | | | | | | | | | | | | |
| 192 | 20 | | PA | 6-0 | 35-21-14 | D00984 | | 2 | | | | | GD00934 | D.. | 2 | | 050-099 |
| 571 | 20 | | PA | 2-0 | 35-21-14 | D10034 | | 1 | | | | | SM00021 | | S | | 280-299 |
| 572 | 20 | | PA | 7-0 | 35-21-14 | D10034 | | 2 | | | | | GD04198 | D.. | 2 | | 280-299 |
| 581 | 20 | | PA | 4-0 | 35-21-14 | D10036 | | 1 | | | | | SM00021 | | S | | 280-299 |
| 582 | 20 | | PA | 7-0 | 35-21-14 | D10036 | | 2 | | | | | GD01940 | D.. | 2 | | 280-299 |
| 601 | 20 | | PA | 8-0 | 35-21-14 | D00982 | | 1 | | | | | SM00023 | | S | | 280-299 |
| 602 | 20 | | PA | 11-0 | 35-21-14 | D00982 | | 2 | | | | | GD01944 | D.. | 2 | | 280-299 |
| 611 | 20 | | PA | 3-0 | 35-21-14 | D00984 | | 1 | | | | | SM00025 | | S | | 280-299 |
| 612 | 20 | | PA | 4-0 | 35-21-14 | D00984 | | 2 | | | | | GD01944 | D.. | 2 | | 280-299 |
| 641 | 20 | | PA | 3-0 | 35-21-14 | D10040 | | 1 | | | | | SM00031 | | S | | 280-299 |
| 642 | 20 | | PA | 5-0 | 35-21-14 | D10040 | | 2 | | | | | GD01944 | D.. | 2 | | 280-299 |
| 651 | 20 | | PA | 4-0 | 35-21-14 | D00986 | | 1 | | | | | SM00031 | | S | | 280-299 |
| 652 | 20 | | PA | 7-0 | 35-21-14 | D00986 | | 2 | | | | | GD01944 | D.. | 2 | | 280-299 |
| 661 | 20 | | PA | 4-0 | 35-21-14 | D10042 | | 1 | | | | | SM00033 | | S | | 280-299 |
| 662 | 20 | | PA | 6-0 | 35-21-14 | D10042 | | 2 | | | | | GD01952 | D.. | 2 | | 280-299 |
| 671 | 20 | | PA | 3-0 | 35-21-14 | D10044 | | 1 | | | | | SM00033 | | S | | 280-299 |
| 672 | 20 | | PA | 4-0 | 35-21-14 | D10044 | | 2 | | | | | GD01952 | D.. | 2 | | 280-299 |
| 681 | 20 | | PA | 5-0 | 35-21-14 | D10046 | | 1 | | | | | SM00033 | | S | | 280-299 |
| 682 | 20 | | PA | 6-0 | 35-21-14 | D10046 | | 2 | | | | | GD01952 | D.. | 2 | | 280-299 |
| W1283 | 286T1283 | | | ELEC SPOILER CONT L2B,SHELF TO CAPT WHL XDCR AND P10 | | | | | | | | | | | | | |
| 001 | 20 | | PA | 3-0 | 27-61-14 | GD00341 | | S.. | E | | | | D00591 | | 6 | | ALL |
| 002 | 20 | | PA | 3-0 | 27-61-14 | GD00641 | | S.. | 2 | | | | D04133J | | 6 | | ALL |
| 003 | 20 | | PA | 0-6 | 27-41-11 | D05133P | | 10 | | | | | SM00001 | | S | | ALL |
| 004 | 20 | | PA | 0-6 | 27-41-11 | D05133P | | 11 | | | | | SM00002 | | S | | ALL |
| 008 | 20 | | PA | 27-0 | 27-41-11 | SM00001 | | | S | | | | TB0207F | A005 | 2 | | ALL |
| 009 | 20 | | PA | 27-0 | 27-41-11 | SM00002 | | | S | | | | TB0207F | C005 | 2 | | ALL |
| 010 | 20 | | PA | 32-0 | 27-41-21 | SM00002 | | | S | | | | TB0307F | C005 | 2 | | ALL |
| 011 | 20 | | PA | 32-0 | 27-41-21 | SM00001 | | | S | | | | TB0307F | A005 | 2 | | ALL |
| 202B | 22 | | PB | IB | 21-0 | 27-61-14 | D05133P | | 9 | | | | D00591 | | 1 | | ALL |
| 202R | 22 | | PB | IB | 0-0 | 27-61-14 | D05133P | | 8 | | | | D00591 | | 2 | | ALL |
| 204B | 22 | | PB | ID | 28-0 | 27-61-14 | D05133P | | 2 | | | | D04133J | | 2 | | ALL |
| 204R | 22 | | PB | ID | 0-0 | 27-61-14 | D05133P | | 1 | | | | D04133J | | 1 | | ALL |
| 301B | 22 | | PC | MA | 21-0 | 27-61-14 | D05133P | | 4 | | | | D00591 | | 4 | | ALL |
| 301R | 22 | | PC | MA | 0-0 | 27-61-14 | D05133P | | 6 | | | | D00591 | | 3 | | ALL |
| 301Y | 22 | | PC | MA | 0-0 | 27-61-14 | D05133P | | 7 | | | | D00591 | | 5 | | ALL |
| 302B | 22 | | PC | MB | 28-0 | 27-61-14 | D05133P | | 15 | | | | D04133J | | 4 | | ALL |
| 302R | 22 | | PC | MB | 0-0 | 27-61-14 | D05133P | | 3 | | | | D04133J | | 3 | | ALL |
| 302Y | 22 | | PC | MB | 0-0 | 27-61-14 | D05133P | | 5 | | | | D04133J | | 5 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1280
Page 13
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1284 | 286T1284 | | | CLOSET LIGHTS | | | | | | | | | | | | |
| 001 | 22 | | PA | 6-0 | 33-22-21 | D06858P | =1 | | | | S00644 | =1 | C | | 162-199 | |
| 002 | 22 | | PA | 3-0 | 33-22-21 | S00644 | =2 | C | | | L00729 | =P | C | | 162-199 | |
| 003 | 22 | | PA | 6-0 | 33-22-21 | D06860J | =1 | | | | L00729 | =G | C | | 162-199 | |
| W1285 | 286T1285 | | | ELEC SPOILER CONT L2C,SHELF TO CAPT WHL XDCR AND P10 | | | | | | | | | | | | |
| 001 | 20 | | PA | 3-0 | 27-61-16 | GD00343 | S.. | E | | | D00593 | | 6 | | ALL | |
| 002 | 20 | | PA | 2-0 | 27-61-16 | GD00641 | S.. | 2 | | | D04135J | | 6 | | ALL | |
| 003 | 22 | | PQ | AC | 5-0 | 27-41-31 | D05135P | | 11 | | SP00427 | | | 9 | 050-099, 155-199, 275-299 | |
| 003Z | | | | AC | 0-0 | 27-41-31 | D05135P | | DED | | SP00427 | | DED | | 050-099, 155-199, 275-299 | |
| 202B | 22 | | PB | IB | 20-0 | 27-61-16 | D05135P | | 9 | | D00593 | | 1 | | ALL | |
| 202R | 22 | | PB | IB | 0-0 | 27-61-16 | D05135P | | 8 | | D00593 | | 2 | | ALL | |
| 204B | 22 | | PB | ID | 27-0 | 27-61-16 | D05135P | | 2 | | D04135J | | 2 | | ALL | |
| 204R | 22 | | PB | ID | 0-0 | 27-61-16 | D05135P | | 1 | | D04135J | | 1 | | ALL | |
| 301B | 22 | | PC | MA | 20-0 | 27-61-16 | D05135P | | 4 | | D00593 | | 4 | | ALL | |
| 301R | 22 | | PC | MA | 0-0 | 27-61-16 | D05135P | | 6 | | D00593 | | 3 | | ALL | |
| 301Y | 22 | | PC | MA | 0-0 | 27-61-16 | D05135P | | 7 | | D00593 | | 5 | | ALL | |
| 302B | 22 | | PC | MB | 27-0 | 27-61-16 | D05135P | | 10 | | D04135J | | 4 | | ALL | |
| 302R | 22 | | PC | MB | 0-0 | 27-61-16 | D05135P | | 3 | | D04135J | | 3 | | ALL | |
| 302Y | 22 | | PC | MB | 0-0 | 27-61-16 | D05135P | | 5 | | D04135J | | 5 | | ALL | |
| W1286 | 286T1286 | | | PARKING BRAKE VALVE R. WHEEL WELL | | | | | | | | | | | | |
| 001 | 20 | | UA | 7-0 | 32-44-11 | D06012P | | | 1 | | D02194 | | 1 | | ALL | |
| 002 | 20 | | UA | 7-0 | 32-44-11 | D06012P | | | 2 | | D02194 | | 2 | | ALL | |
| 003 | 20 | | UA | 7-0 | 32-44-11 | D06012P | | | 3 | | D02194 | | 3 | | ALL | |
| 004 | 20 | | UA | 7-0 | 32-44-11 | D06012P | | | 4 | | D02194 | | 4 | | ALL | |
| 008 | 20 | | UA | 7-0 | 32-44-11 | D06012P | | | 8 | | D02194 | | 8 | | ALL | |
| 009 | 20 | | UA | 7-0 | 32-44-11 | D06012P | | | 9 | | D02194 | | 9 | | ALL | |
| 010 | 20 | | UA | 7-0 | 32-44-11 | D06012P | | | 10 | | D02194 | | 10 | | ALL | |
| W1287 | 286T1287 | | | CONFIGURATION WARNING,P10,P51,TO SHELF | | | | | | | | | | | | |
| 002 | 24 | | PK | 20-0 | 27-32-11 | D05281J | | | 2 | | D04511P | | 2 | | ALL | |
| 003 | 24 | | PK | 20-0 | 27-32-11 | D05281J | | | 3 | | D04511P | | 3 | | ALL | |
| 004 | 24 | | PK | 20-0 | 27-32-11 | D05281J | | | 4 | | D04511P | | 4 | | ALL | |
| 008 | 24 | | PK | 36-0 | 31-51-41 | S00459 | | 2NC | B | | D04511P | | 14 | | ALL | |
| 009 | 20 | | PA | 2-0 | 31-51-41 | S00459 | | 2C | B | | GD00623 | | A.. | E | 050-099, 150-199 | |
| 009 | 20 | | PA | 3-0 | 31-51-41 | S00459 | | 2C | B | | GD00623 | | A.. | E | 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W1280

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------|-------|---------|-------|------|------|--------|-------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |

| W1287 | 286T1287 | | | CONFIGURATION WARNING,P10,P51,TO SHELF (continued) | | | | | | | | | | | | |
|-------|----------|--|----|--|------|----------|---------|--|--|----|--|---------|--|--|----|---------|
| 010 | 24 | | PK | | 20-0 | SPARE | D05281J | | | 5 | | D04511P | | | 5 | ALL |
| 011 | 24 | | PK | | 20-0 | SPARE | D05281J | | | 6 | | D04511P | | | 6 | ALL |
| 012 | 24 | | PK | | 20-0 | SPARE | D05281J | | | 1 | | D04511P | | | 18 | ALL |
| 013 | 24 | | PK | | 20-0 | SPARE | D05281J | | | 9 | | D04511P | | | 19 | ALL |
| 014 | 24 | | PK | | 20-0 | 31-51-42 | D05281J | | | 11 | | D04511P | | | 11 | ALL |
| 015 | 24 | | PK | | 20-0 | 31-51-41 | D05281J | | | 12 | | D04511P | | | 12 | ALL |
| 016 | 24 | | PK | | 20-0 | SPARE | D05281J | | | 10 | | D04511P | | | 10 | ALL |
| 017 | 24 | | PK | | 20-0 | 27-32-21 | D05281J | | | 13 | | D04511P | | | 13 | ALL |
| 018 | 24 | | PK | | 20-0 | 27-32-21 | D05281J | | | 14 | | D04511P | | | 16 | ALL |
| 019 | 24 | | PK | | 20-0 | 27-32-21 | D05281J | | | 15 | | D04511P | | | 15 | ALL |
| 020 | 24 | | PK | | 20-0 | SPARE | D04511P | | | 20 | | D05281J | | | 20 | 050-099 |
| 021 | 24 | | PK | | 20-0 | SPARE | D04511P | | | 21 | | D05281J | | | 21 | 050-099 |
| 201B | 24 | | PL | IA | 20-0 | 27-32-21 | D05281J | | | 8 | | D04511P | | | 8 | ALL |
| 201R | 24 | | PL | IA | 0-0 | 27-32-21 | D05281J | | | 7 | | D04511P | | | 7 | ALL |
| 247B | 24 | | PW | JV | 23-0 | 32-45-11 | D04511P | | | 23 | | D06804J | | | 2 | 275-299 |
| 247R | 24 | | PW | JV | 0-0 | 32-45-11 | D04511P | | | 22 | | D06804J | | | 1 | 275-299 |
| 247Z | | | | JV | 0-0 | 32-45-11 | D04511P | | | 24 | | D06804J | | | 3 | 275-299 |

| W1288 | 286T1288 | | | L LOGO LIGHTS | | | | | | | | | | | | |
|-------|----------|--|----|---------------|------|----------|---------|--|-----|---|--|---------|--|------|---|-----|
| 001 | 16 | | UA | | 41-0 | 33-45-11 | SP01962 | | | 9 | | L00432 | | 110V | N | ALL |
| 002 | 10 | | UA | | 8-0 | 33-45-11 | L00432 | | 13V | N | | L00433 | | 13V | N | ALL |
| 003 | 10 | | UA | | 6-0 | 33-45-11 | L00432 | | RTN | N | | GD04182 | | A.. | N | ALL |
| 004 | 10 | | UA | | 6-0 | 33-45-11 | L00432 | | GND | N | | GD04184 | | S.. | N | ALL |
| 005 | 10 | | UA | | 4-0 | 33-45-11 | L00433 | | GND | N | | GD04184 | | S.. | N | ALL |
| 006 | 10 | | UA | | 4-0 | 33-45-11 | L00433 | | RTN | N | | GD04182 | | A.. | N | ALL |

WIRE LIST
D280T132

91-21-11
Section W1280
Page 15 End
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|--|----|------|-------------|----------|---------|------|------|---------|-------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1290 | 286T1290 | R LOGO LIGHTS | | | | | | | | | | | | | | |
| 001 | 16 | | UA | 42-0 | 33-45-11 | SP01964 | | | 9 | L00434 | 110V | N | | ALL | | |
| 002 | 10 | | UA | 7-4 | 33-45-11 | L00434 | | 13V | N | L00435 | 13V | N | | ALL | | |
| 003 | 10 | | UA | 6-0 | 33-45-11 | L00434 | | RTN | N | GD04186 | A.. | N | | ALL | | |
| 004 | 10 | | UA | 6-0 | 33-45-11 | L00434 | | GND | N | GD04188 | S.. | N | | ALL | | |
| 005 | 10 | | UA | 4-0 | 33-45-11 | L00435 | | GND | N | GD04188 | S.. | N | | ALL | | |
| 006 | 10 | | UA | 4-0 | 33-45-11 | L00435 | | RTN | N | GD04186 | A.. | N | | ALL | | |
| W1291 | 286T1291 | ELEC SPOILER CONT R2A,SHELF TO F/O WHL XDCR AND P10 | | | | | | | | | | | | | | |
| 001 | 20 | | PA | 2-2 | 27-61-17 | GD00345 | | S.. | E | D00595 | 6 | | | ALL | | |
| 002 | 20 | | PA | 1-8 | 27-61-17 | GD00641 | | S.. | 2 | D04137J | 6 | | | ALL | | |
| 202B | 22 | | PB | IB | 20-1 | 27-61-17 | D05137P | | 9 | D00595 | 1 | | | ALL | | |
| 202R | 22 | | PB | IB | 0-0 | 27-61-17 | D05137P | | 8 | D00595 | 2 | | | ALL | | |
| 204B | 22 | | PB | ID | 39-5 | 27-61-17 | D05137P | | 2 | D04137J | 2 | | | ALL | | |
| 204R | 22 | | PB | ID | 0-0 | 27-61-17 | D05137P | | 1 | D04137J | 1 | | | ALL | | |
| 301B | 22 | | PC | MA | 20-1 | 27-61-17 | D05137P | | 4 | D00595 | 4 | | | ALL | | |
| 301R | 22 | | PC | MA | 0-0 | 27-61-17 | D05137P | | 6 | D00595 | 3 | | | ALL | | |
| 301Y | 22 | | PC | MA | 0-0 | 27-61-17 | D05137P | | 7 | D00595 | 5 | | | ALL | | |
| 302B | 22 | | PC | MB | 39-5 | 27-61-17 | D05137P | | 10 | D04137J | 4 | | | ALL | | |
| 302R | 22 | | PC | MB | 0-0 | 27-61-17 | D05137P | | 3 | D04137J | 3 | | | ALL | | |
| 302Y | 22 | | PC | MB | 0-0 | 27-61-17 | D05137P | | 5 | D04137J | 5 | | | ALL | | |
| W1293 | 286T1293 | ELEC SPOILER CONT R2B,SHELF TO F/O WHL XDCR AND P10 | | | | | | | | | | | | | | |
| 001 | 20 | | PA | 3-0 | 27-61-13 | GD00347 | | S.. | E | D00597 | 6 | | | ALL | | |
| 002 | 20 | | PA | 4-0 | 27-61-13 | GD00641 | | S.. | 2 | D04139J | 6 | | | ALL | | |
| 003Y | 22 | | PJ | 40-0 | 27-41-21 | D05139P | | 10 | | SP00105 | | 9 | | ALL | | |
| 006Y | 22 | | PJ | 40-0 | 27-41-21 | D05139P | | 13 | | SP00107 | | 9 | | ALL | | |
| 007Y | 22 | | PJ | 40-0 | 27-41-21 | D05139P | | 14 | | SP00031 | | 9 | | ALL | | |
| 202B | 22 | | PB | IB | 20-0 | 27-61-13 | D05139P | | 9 | D00597 | 1 | | | ALL | | |
| 202R | 22 | | PB | IB | 0-0 | 27-61-13 | D05139P | | 8 | D00597 | 2 | | | ALL | | |
| 204B | 22 | | PB | ID | 39-0 | 27-61-13 | D05139P | | 2 | D04139J | 2 | | | ALL | | |
| 204R | 22 | | PB | ID | 0-0 | 27-61-13 | D05139P | | 1 | D04139J | 1 | | | ALL | | |
| 301B | 22 | | PC | MA | 20-0 | 27-61-13 | D05139P | | 4 | D00597 | 4 | | | ALL | | |
| 301R | 22 | | PC | MA | 0-0 | 27-61-13 | D05139P | | 6 | D00597 | 3 | | | ALL | | |
| 301Y | 22 | | PC | MA | 0-0 | 27-61-13 | D05139P | | 7 | D00597 | 5 | | | ALL | | |
| 302B | 22 | | PC | MB | 39-0 | 27-61-13 | D05139P | | 12 | D04139J | 4 | | | ALL | | |
| 302R | 22 | | PC | MB | 0-0 | 27-61-13 | D05139P | | 3 | D04139J | 3 | | | ALL | | |
| 302Y | 22 | | PC | MB | 0-0 | 27-61-13 | D05139P | | 5 | D04139J | 5 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W1290

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------|--|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1294 | 286T1294 | | | | NOSE GR TORQUE LINK,TAXI LT | | | | | | | | | | | |
| 207B | 20 | VG | IG | 7-0 | 32-45-12 | D06106J | 8 | | | D13376 | 2 | | | 050-099, 155-156, 163-199, 275-299 | | |
| 207R | 20 | VG | IG | 0-0 | 32-45-12 | D06106J | 9 | | | D13376 | 1 | | | 050-099, 155-156, 163-199, 275-299 | | |
| 207Z | | | IG | 0-0 | 32-45-12 | D06106J | 10 | | | D13376 | 3 | | | 050-099, 155-156, 163-199, 275-299 | | |
| 208B | 20 | VG | IH | 7-0 | 32-45-12 | D06106J | 11 | | | D13374 | 2 | | | 050-099, 155-156, 163-199, 275-299 | | |
| 208R | 20 | VG | IH | 0-0 | 32-45-12 | D06106J | 12 | | | D13374 | 1 | | | 050-099, 155-156, 163-199, 275-299 | | |
| 208Z | | | IH | 0-0 | 32-45-12 | D06106J | 13 | | | D13374 | 3 | | | 050-099, 155-156, 163-199, 275-299 | | |
| W1295 | 286T1295 | | | | ELEC SPOILER CONT R2C,SHELF TO F/O WHL XDCR AND P10 | | | | | | | | | | | |
| 001 | 20 | PA | | 1-10 | 27-61-18 | GD00349 | S.. | E | | D00599 | 6 | | | ALL | | |
| 002 | 20 | PA | | 1-4 | 27-61-18 | GD00641 | S.. | 2 | | D04141J | 6 | | | ALL | | |
| 202B | 22 | PB | IB | 21-1 | 27-61-18 | D05141P | 9 | | | D00599 | 1 | | | ALL | | |
| 202R | 22 | PB | IB | 0-0 | 27-61-18 | D05141P | 8 | | | D00599 | 2 | | | ALL | | |
| 204B | 22 | PB | ID | 40-11 | 27-61-18 | D05141P | 2 | | | D04141J | 2 | | | ALL | | |
| 204R | 22 | PB | ID | 0-0 | 27-61-18 | D05141P | 1 | | | D04141J | 1 | | | ALL | | |
| 301B | 22 | PC | MA | 21-1 | 27-61-18 | D05141P | 4 | | | D00599 | 4 | | | ALL | | |
| 301R | 22 | PC | MA | 0-0 | 27-61-18 | D05141P | 6 | | | D00599 | 3 | | | ALL | | |
| 301Y | 22 | PC | MA | 0-0 | 27-61-18 | D05141P | 7 | | | D00599 | 5 | | | ALL | | |
| 302B | 22 | PC | MB | 40-11 | 27-61-18 | D05141P | 10 | | | D04141J | 4 | | | ALL | | |
| 302R | 22 | PC | MB | 0-0 | 27-61-18 | D05141P | 3 | | | D04141J | 3 | | | ALL | | |
| 302Y | 22 | PC | MB | 0-0 | 27-61-18 | D05141P | 5 | | | D04141J | 5 | | | ALL | | |
| W1296 | 286T1296 | | | | FIRE DET-APU LOOP 1 | | | | | | | | | | | |
| 001R | 20 | XG | | 39-8 | 26-15-11 | D06110J | 1 | | | D04020J | 1 | | | ALL | | |
| 002R | 20 | XG | | 39-8 | 26-15-11 | D06110J | 3 | | | D04020J | 3 | | | ALL | | |
| 003R | 20 | XG | | 39-8 | 26-15-11 | D06110J | 2 | | | D04020J | 2 | | | ALL | | |
| 004R | 20 | XG | | 41-9 | 26-22-21 | D06110J | 4 | | | D01436 | 1 | | | ALL | | |
| 005R | 18 | XG | | 3-10 | 26-22-21 | D01436 | 2 | DK | | GD00034 | D.. | N | | ALL | | |
| 006R | 18 | XG | | 4-0 | 26-22-21 | D01436 | 3 | DK | | GD00036 | S.. | N | | ALL | | |
| 007R | 18 | XG | | 4-6 | 26-22-21 | D01438 | 4 | DK | | GD00036 | S.. | N | | 050-099, 150-199 | | |
| 007R | 18 | XG | | 4-0 | 26-22-21 | D01438 | 4 | DK | | GD00036 | S.. | N | | 275-299 | | |
| 008R | 18 | XG | | 3-10 | 26-22-21 | D01438 | 3 | DK | | GD04298 | D.. | N | | 050-099, 150-199 | | |
| 008R | 18 | XG | | 3-4 | 26-22-21 | D01438 | 3 | DK | | GD04298 | D.. | N | | 275-299 | | |
| 009R | 20 | XG | | 42-2 | 26-22-21 | D01438 | 1 | | | D06110J | 5 | | | 050-099, 150-199 | | |

WIRE LIST
D280T132

91-21-11
Section W1290
Page 2
Mar 14/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1296 | 286T1296 | | | FIRE DET-APU LOOP 1 (continued) | | | | | | | | | | | | | |
| 009R | 20 | | XG | 41-9 | 26-22-21 | D01438 | | | | 1 | | | D06110J | 5 | | | 275-299 |
| 010R | 20 | | XG | 39-8 | SPARE | D04020J | | | | 9 | | | D06110J | 9 | | | ALL |
| 011R | 20 | | XG | 39-8 | SPARE | D04020J | | | | 10 | | | D06110J | 10 | | | ALL |
| 012R | 20 | | XG | 50-6 | 26-22-21 | D02064 | | | | 1 | | | D06110J | 6 | | | 275-299 |
| 013R | 18 | | XG | 3-8 | 26-22-21 | D02064 | | | | 2 | DK | | GD03914 | D.. | N | | 275-299 |
| 014R | 18 | | XG | 3-11 | 26-22-21 | D02064 | | | | 3 | DK | | GD03912 | S.. | N | | 275-299 |
| 015R | 18 | | XG | 4-5 | 26-22-21 | D02066 | | | | 4 | DK | | GD03912 | S.. | N | | 275-299 |
| 016R | 18 | | XG | 4-2 | 26-22-21 | D02066 | | | | 3 | DK | | GD04300 | D.. | N | | 275-299 |
| 017R | 20 | | XG | 51-6 | 26-22-21 | D02066 | | | | 1 | | | D06110J | 7 | | | 275-299 |
| 018R | 18 | | XG | 47-4 | 26-18-31 | D06110J | | | | 8 | DL | | D01508 | =1 | | | ALL |
| 019 | 20 | | UA | 22-8 | 38-32-11 | SP01632 | | | | 9 | | | D03598 | 3 | | | 050-099 |
| 019 | 20 | | UA | 21-10 | 38-32-11 | SP01632 | | | | 9 | | | D03598 | 3 | | | 150-199, 275-299 |
| 020 | 20 | | UA | 22-8 | 38-32-11 | SP01816 | | | | 9 | | | D03598 | 2 | | | 050-099 |
| 020 | 20 | | UA | 21-10 | 38-32-11 | SP01816 | | | | 9 | | | D03598 | 2 | | | 150-199, 275-299 |
| W1297 | 286T1297 | | | CONT COLUMN SHAKER M240 | | | | | | | | | | | | | |
| 001 | 20 | | PA | 17-0 | 27-32-11 | SP00221 | | | | 9 | | | D00695 | A | \$D | | ALL |
| 002 | 20 | | PA | 26-0 | 27-32-11 | SP00223 | | | | 9 | | | D00695 | B | \$D | | ALL |
| W1298 | 286T1298 | | | FIRE DET-APU LOOP 2 | | | | | | | | | | | | | |
| 001R | 20 | | XG | 39-6 | 26-15-11 | D06112J | | | | 2 | | | D04022J | 2 | | | ALL |
| 002R | 20 | | XG | 39-6 | 26-15-11 | D06112J | | | | 3 | | | D04022J | 3 | | | ALL |
| 003R | 20 | | XG | 39-6 | 26-15-11 | D06112J | | | | 1 | | | D04022J | 1 | | | ALL |
| 004R | 20 | | XG | 39-6 | SPARE | D06112J | | | | 4 | | | D04022J | 4 | | | ALL |
| 006 | 20 | | UA | 19-6 | 38-32-11 | D01270 | | | | 2 | | | SP00602 | | 9 | | ALL |
| 007 | 20 | | UA | 21-2 | 38-32-11 | D01270 | | | | 3 | | | SP00738 | | 9 | | ALL |
| 201B | 20 | | VG | A | 37-0 | 23-41-11 | D04022J | | | 5 | | | SP00187 | | S | | ALL |
| 201R | 20 | | VG | A | 0-0 | 23-41-11 | D04022J | | | 6 | | | SP00185 | | S | | ALL |
| 201Z | | | | A | 0-0 | 23-41-11 | D04022J | | | 7 | | | SP00189 | | S | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1290
Page 3 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1300 | 286T1300 | | | LEFT SURGE TANK SPILL DETECTION | | | | | | | | | | | |
| 001 | 20 | 98 | | A | 84-0 | 28-21-12 | D08306J | | | | TB5128 | 3 | N | | ALL |
| 001Z | | | | A | 0-0 | 28-21-12 | D08306J | | | | TB5128 | DED | | | ALL |
| 002 | 20 | 98 | | C | 84-0 | 28-21-12 | D08306J | | | | TB5128 | 1 | N | | ALL |
| 002Z | | | | C | 0-0 | 28-21-12 | D08306J | | | FA | TB5128 | 2 | N | | ALL |
| A-A | | | | B | 0-0 | 28-21-12 | TS0195 | | YEL | | TB5128 | 3 | N | | ALL |
| A-B | | | | B | 0-0 | 28-21-12 | TS0195 | | GRN | | TB5128 | 2 | N | | ALL |
| A-C | | | | B | 0-0 | 28-21-12 | TS0195 | | WHT | | TB5128 | 1 | N | | ALL |
| FRA | | | | | 0-0 | 28-21-12 | D08306J | | | | D08306J | | | FA | ALL |
| FRB | | | | | 0-0 | 28-21-12 | D08306J | | | | D08306J | | | FA | ALL |
| FRC | | | | | 0-0 | 28-21-12 | D08306J | | | | D08306J | | | FA | ALL |
| W1302 | 286T1302 | | | RIGHT SURGE TANK SPILL DETECTION | | | | | | | | | | | |
| 001 | 20 | 98 | | A | 84-0 | 28-21-12 | D08308J | | | | TB5126 | 3 | N | | ALL |
| 001Z | | | | A | 0-0 | 28-21-12 | D08308J | | | | TB5126 | DED | | | ALL |
| 002 | 20 | 98 | | C | 84-0 | 28-21-12 | D08308J | | | | TB5126 | 1 | N | | ALL |
| 002Z | | | | C | 0-0 | 28-21-12 | D08308J | | | FA | TB5126 | 2 | N | | ALL |
| A-A | | | | B | 0-0 | 28-21-12 | TS0196 | | YEL | | TB5126 | 3 | N | | ALL |
| A-B | | | | B | 0-0 | 28-21-12 | TS0196 | | GRN | | TB5126 | 2 | N | | ALL |
| A-C | | | | B | 0-0 | 28-21-12 | TS0196 | | WHT | | TB5126 | 1 | N | | ALL |
| FRA | | | | | 0-0 | 28-21-12 | D08308J | | | | D08308J | | | FA | ALL |
| FRB | | | | | 0-0 | 28-21-12 | D08308J | | | | D08308J | | | FA | ALL |
| FRC | | | | | 0-0 | 28-21-12 | D08308J | | | | D08308J | | | FA | ALL |
| W1304 | 286T1304 | | | NOSE GEAR LANDING & TAXI LIGHTS | | | | | | | | | | | |
| 001 | 10 | | UA | | 8-0 | 33-42-11 | L00114 | =P | M | | TB5124 | 3 | N | | ALL |
| 002 | 10 | | UA | | 8-0 | 33-42-11 | L00114 | =G | M | | TB5124 | 2 | N | | ALL |
| 003 | 10 | | UA | | 8-0 | 33-42-11 | L00113 | =P | M | | TB5120 | 3 | N | | ALL |
| 004 | 10 | | UA | | 8-0 | 33-42-11 | L00113 | =G | M | | TB5120 | 2 | N | | ALL |
| 005 | 16 | | UA | | 6-0 | 33-42-21 | L00622 | =P | M | | TB5122 | 4 | N | | ALL |
| 006 | 16 | | UA | | 6-0 | 33-42-21 | L00622 | =G | M | | TB5124 | 5 | N | | ALL |
| 007 | 16 | | UA | | 6-0 | 33-42-21 | L00621 | =P | M | | TB5122 | 5 | N | | ALL |
| 008 | 16 | | UA | | 6-0 | 33-42-21 | L00621 | =G | M | | TB5120 | 5 | N | | ALL |
| W1306 | 286T1306 | | | LDG GR ALTERNATE EXT RLY & SW | | | | | | | | | | | |
| 001 | 18 | | PA | | 5-0 | 32-35-11 | D06198J | | | | S00606 | COM | C | | ALL |
| 003 | 12 | | PA | | 5-0 | 32-35-11 | D06198J | | | | S00607 | COM | C | | ALL |
| 008 | 16 | | PA | | 4-0 | 32-35-11 | S00606 | | NC | C | D10228 | 3 | | | ALL |
| 009 | 16 | | PA | | 3-0 | 32-35-11 | GD04480 | | D.. | E | D10228 | 1 | | | ALL |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1306 | 286T1306 | | | LDG GR ALTERNATE EXT RLY & SW (continued) | | | | | | | | | | | | |
| 010 | 16 | | PA | 3-0 | 32-35-11 | GD04482 | S.. | E | | D10228 | 7 | | | ALL | | |
| 011 | 16 | | PA | 4-0 | 32-35-11 | S00607 | NC | C | | D10228 | 5 | | | ALL | | |
| W1307 | 286T1307 | | | YAW DAMPER NO.1,P5 TO SHELF | | | | | | | | | | | | |
| 001 | 20 | | PA | 40-0 | 22-21-11 | D05307P | | | 1 | D00723 | 5 | | | ALL | | |
| 002 | 22 | | PA | 40-0 | 22-21-11 | D05307P | | | 2 | D00723 | 7 | | | ALL | | |
| 003 | 22 | | PA | 38-0 | 22-21-11 | D05307P | | | 3 | TB0066X | A009 | BJ | | ALL | | |
| 005 | 22 | | PA | 38-0 | 27-11-12 | D05307P | | | 4 | TB0068X | C009 | BJ | | ALL | | |
| 006 | 22 | | PA | 38-0 | 27-21-12 | D05307P | | | 5 | TB0068X | D009 | BJ | | ALL | | |
| 007 | 22 | | PA | 38-0 | 27-41-11 | D05307P | | | 10 | TB0068X | C010 | BJ | | ALL | | |
| 008 | 22 | | PA | 38-0 | 27-61-12 | D05307P | | | 6 | TB0068X | A009 | BJ | | ALL | | |
| 009 | 20 | | PA | 8-0 | 22-21-11 | D00723 | | | 6 | TB0068X | B010 | BJ | | ALL | | |
| 010 | 24 | | PK | 20-0 | 27-09-14 | D05307P | | | 11 | D05051P | A05 | \$D | | ALL | | |
| 011 | 24 | | PK | 20-0 | 27-09-14 | D05307P | | | 8 | D05051P | A04 | \$D | | ALL | | |
| 013 | 24 | | PK | 20-0 | 27-61-12 | D05307P | | | 12 | D05051P | A09 | \$D | | ALL | | |
| 014 | 24 | | PK | 20-0 | 27-41-11 | D05307P | | | 13 | D05051P | A07 | \$D | | ALL | | |
| 015 | 24 | | PK | 20-0 | 27-41-11 | D05307P | | | 14 | D05051P | A08 | \$D | | ALL | | |
| 016 | 24 | | PK | 20-0 | SPARE | D05307P | | | 15 | D05051P | A03 | \$D | | ALL | | |
| 017 | 24 | | PK | 20-0 | 27-11-12 | D05307P | | | 21 | D05051P | A06 | \$D | | ALL | | |
| 018 | 20 | | PA | 15-0 | 27-11-12 | D05307P | | | 16 | D05165P | 1 | | | ALL | | |
| 019 | 20 | | PA | 15-0 | 27-11-12 | D05307P | | | 17 | D05165P | 2 | | | ALL | | |
| 020 | 18 | | PA | 15-0 | 27-11-12 | D05307P | | | 18 | D05165P | 3 | DK | | ALL | | |
| 021 | 18 | | PA | 15-0 | 27-11-12 | D05307P | | | 19 | D05165P | 4 | DK | | ALL | | |
| 022 | 22 | | PA | 15-0 | SPARE | D05307P | | | 20 | D05165P | 5 | | | ALL | | |
| 023 | 24 | | PK | 20-0 | 22-21-11 | D05307P | | | 22 | D05051P | A02 | \$D | | ALL | | |
| 024 | 24 | | PK | 20-0 | 27-21-12 | D05307P | | | 23 | D05051P | A10 | \$D | | ALL | | |
| 025 | 22 | | PA | 38-0 | 27-41-11 | D05307P | | | 24 | TB0068X | D010 | BJ | | ALL | | |
| 030 | 22 | | PA | 8-0 | 33-16-17 | D00723 | | | 3 | TB0068Y | A020 | BJ | | ALL | | |
| 031 | 22 | | PA | 8-0 | 33-16-17 | D00723 | | | 4 | TB0068Z | 21 | BJ | | ALL | | |
| 032 | 20 | | PA | 7-0 | 22-21-11 | D00723 | | | 12 | GD00092 | D.. | 2 | | ALL | | |
| 036 | 22 | | PA | 9-0 | 31-31-18 | D05307P | | | 26 | D05225J | 6 | | | ALL | | |
| 037 | 22 | | PA | 9-0 | 31-31-18 | D05307P | | | 27 | D05225J | 5 | | | ALL | | |
| 038 | 22 | | PA | 9-0 | 31-31-18 | D05307P | | | 28 | D05225J | 4 | | | ALL | | |
| 039 | 22 | | PA | 9-0 | 31-31-18 | D05307P | | | 29 | D05225J | 2 | | | ALL | | |
| 040 | 22 | | PA | 9-0 | 31-31-18 | D05307P | | | 30 | D05225J | 1 | | | ALL | | |
| 041 | 22 | | PA | 9-0 | 31-31-18 | D05307P | | | 31 | D05225J | 3 | | | ALL | | |
| 042 | 24 | | PK | 13-0 | SPARE | D05165P | | | 7 | D05051P | A11 | \$D | | ALL | | |
| 043 | 24 | | PK | 20-0 | SPARE | D05307P | | | 7 | D05051P | A12 | \$D | | ALL | | |
| 044 | 24 | | PK | 20-0 | 27-09-14 | D05307P | | | 25 | D05051P | A13 | \$D | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W1300

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1307 | 286T1307 | | | YAW DAMPER NO.1,P5 TO SHELF (continued) | | | | | | | | | | | |
| 049 | 24 | | PK | | 20-0 | 27-09-14 | D05307P | | 34 | | D05051P | A14 | \$D | | ALL |
| 050 | 24 | | PK | | 20-0 | 27-09-14 | D05307P | | 35 | | D05051P | A15 | \$D | | ALL |
| 051 | 24 | | PK | | 20-0 | 27-09-14 | D05307P | | 36 | | D05051P | A16 | \$D | | ALL |
| 052 | 24 | | PK | | 1-0 | SPARE | D05051P | CAP | Y | | D05051P | A17 | \$D | | ALL |
| 053 | 24 | | PK | | 1-0 | SPARE | D05051P | CAP | Y | | D05051P | A18 | \$D | | ALL |
| 054 | 24 | | PK | | 1-0 | SPARE | D05051P | CAP | Y | | D05051P | A19 | \$D | | ALL |
| 055 | 20 | | PA | | 8-0 | 33-13-16 | D00723 | | 1 | | TB0068H | 3 | 2 | | ALL |
| 056 | 20 | | PA | | 7-0 | 33-13-16 | D00723 | | 2 | | GD00263 | A.. | 2 | | ALL |
| 100 | 24 | | PV | PI | 42-0 | 34-61-14 | D05225J | | 9 | | TB0070X | B009 | BJ | | 050-099, 150-199, 276-299 |
| 100Z | | | | PI | 0-0 | 34-61-14 | D05225J | | DED | | TB0070X | DED | | | 050-099, 150-199, 276-299 |
| 124 | 24 | | PK | | 15-0 | SPARE | D05307P | | 37 | | D05165P | 6 | | | 150-199 |
| W1308 | 286T1308 | | | ELEC HYD PUMP | | | | | | | | | | | |
| 301B | 18 | | UC | AA | 13-0 | 29-11-31 | D06280P | | 1 | | D00920 | 2 | | | ALL |
| 301R | 18 | | UC | AA | 0-0 | 29-11-31 | D06280P | | 7 | | D00920 | 1 | | | ALL |
| 301Y | 18 | | UC | AA | 0-0 | 29-11-31 | D06280P | | 4 | | D00920 | 3 | | | ALL |
| W1309 | 286T1309 | | | YAW DAMPER NO.2,P5 TO SHELF | | | | | | | | | | | |
| 001 | 20 | | PA | | 8-0 | 22-21-21 | D00725 | | 6 | | TB0066X | B008 | BJ | | ALL |
| 002 | 20 | | PA | | 36-0 | 22-21-21 | D04843P | | 1 | | D00725 | 5 | | | ALL |
| 003 | 22 | | PA | | 36-0 | 22-21-21 | D04843P | | 2 | | D00725 | 7 | | | ALL |
| 004 | 22 | | PA | | 34-0 | 22-21-21 | D04843P | | 3 | | TB0070X | A009 | BJ | | ALL |
| 006 | 22 | | PA | | 8-0 | 33-16-17 | D00725 | | 3 | | TB0066Z | 33 | BJ | | ALL |
| 007 | 22 | | PA | | 8-0 | 33-16-17 | D00725 | | 4 | | TB0066Z | 34 | BJ | | ALL |
| 010 | 20 | | PA | | 8-0 | 22-21-21 | D00725 | | 12 | | GD00092 | D.. | 2 | | ALL |
| 016 | 22 | | PA | | 34-0 | 27-61-12 | D04843P | | 4 | | TB0066X | C008 | BJ | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1300
Page 3 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|--|----|-----|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1311 | 286T1311 | TMC,ALT ALERT & GWPS FWD PNL'S TO SHELVES & P51 | | | | | | | | | | | | | | | | |
| 001 | 20 | | UA | | 1-6 | 22-14-11 | GD00401 | | S.. | 2 | | | | D05255J | | | FA | ALL |
| 003 | 22 | | PA | | 29-0 | SPARE | D05259J | | | 1 | | | | D05255J | | 1 | | ALL |
| 004 | 24 | | PK | | 44-0 | 31-51-43 | D04507P | | | 10 | | | | D05255J | | 18 | | ALL |
| 005 | 24 | | PK | | 44-0 | 31-51-21 | D04507P | | | 5 | | | | D05255J | | 42 | | ALL |
| 006 | 24 | | PK | | 44-0 | 31-51-21 | D04507P | | | 3 | | | | D05255J | | 43 | | ALL |
| 007 | 24 | | PK | | 44-0 | 31-51-42 | D04507P | | | 6 | | | | D05255J | | 27 | | ALL |
| 009 | 24 | | PK | | 44-0 | 34-16-11 | D04507P | | | 2 | | | | D05255J | | 32 | | ALL |
| 010 | 22 | | PA | | 29-0 | 34-46-11 | D05257J | | | 1 | | | | D05255J | | 20 | | ALL |
| 011 | 22 | | PA | | 29-0 | 34-46-11 | D05257J | | | 2 | | | | D05255J | | 21 | | ALL |
| 012 | 24 | | PK | | 29-0 | 34-46-11 | D05257J | | | 3 | | | | D05255J | | 22 | | ALL |
| 013 | 22 | | PA | | 29-0 | 34-46-11 | D05257J | | | 4 | | | | D05255J | | 23 | | ALL |
| 014 | 22 | | PA | | 29-0 | SPARE | D05259J | | | 21 | | | | D05255J | | 31 | | ALL |
| 015 | 20 | | UA | | 3-0 | 22-14-11 | GD00301 | | S.. | 2 | | | | D04507P | | | FB | ALL |
| 017 | 24 | | PK | | 22-0 | 31-31-22 | D04445J | | | 2 | | | | D04507P | | 1 | | 050-099, 275-299 |
| 017 | 24 | | PK | | 22-0 | 31-31-18 | D04507P | | | 1 | | | | D04445J | | 2 | | 150-199 |
| 018 | 22 | | PA | | 28-0 | SPARE | D04507P | | | 4 | | | | D05259J | | 24 | | ALL |
| 020 | 24 | | PK | | 32-0 | 34-61-16 | D05255J | | | 19 | | | | D04445J | | 15 | | ALL |
| 021 | 24 | | PK | | 32-0 | 34-61-16 | D05255J | | | 24 | | | | D04445J | | 16 | | ALL |
| 022 | 24 | | PK | | 32-0 | 34-61-26 | D05255J | | | 26 | | | | D04445J | | 10 | | 050-099, 155-199, 277-299 |
| 022 | 24 | | PK | | 37-0 | 34-61-26 | D05255J | | | 26 | | | | D04445J | | 10 | | 275-276 |
| 023 | 24 | | PK | | 32-0 | 34-61-16 | D05255J | | | 25 | | | | D04445J | | 9 | | 050-099, 155-199, 277-299 |
| 023 | 24 | | PK | | 37-0 | 34-61-16 | D05255J | | | 25 | | | | D04445J | | 9 | | 275-276 |
| 027 | 24 | | PK | | 29-0 | 34-12-12 | D05259J | | | 27 | | | | D05255J | | 37 | | ALL |
| 028 | 22 | | PA | | 32-0 | 34-61-15 | D05255J | | | 38 | | | | D04445J | | 8 | | ALL |
| 031 | 24 | | PK | | 7-0 | 31-31-19 | D04445J | | | 24 | | | | SM00002 | | 9 | | ALL |
| 034 | 24 | | PK | | 28-0 | 34-13-21 | D05255J | | | 44 | | | | SM00002 | | 9 | | ALL |
| 035 | 24 | | PK | | 17-0 | 34-13-21 | D04507P | | | 7 | | | | SM00002 | | 9 | | ALL |
| 036 | 22 | | PA | | 31-0 | 34-12-61 | D05255J | | | 53 | | | | D05259J | | 10 | | ALL |
| 037 | 22 | | PA | | 31-0 | 34-12-61 | D05255J | | | 54 | | | | D05259J | | 11 | | ALL |
| 200 | 20 | | UA | | 1-6 | 34-45-14 | GD00401 | | S.. | 2 | | | | D05255J | | | HY | 050-099, 150-199, 277-299 |
| 200B | 24 | | PW | HY | 29-0 | 34-45-14 | D05259J | | | 28 | | | | D05255J | | 47 | | 050-099, 150-199, 277-299 |
| 200R | 24 | | PW | HY | 0-0 | 34-45-14 | D05259J | | | 25 | | | | D05255J | | 46 | | 050-099, 150-199, 277-299 |
| 200Z | | | | HY | 0-0 | 34-45-14 | D05259J | | | 29 | | | | D05255J | | | HY | 050-099, 150-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W1310

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|-----------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1311 | 286T1311 | | | TMC,ALT ALERT & GWPS FWD PNL'S TO SHELVES & P51 (continued) | | | | | | | | | | | |
| 201B | 24 | PW | IA | 44-0 | 22-14-11 | D05255J | 40 | | | D04507P | 8 | | | ALL | |
| 201R | 24 | PW | IA | 0-0 | 22-14-11 | D05255J | 39 | | | D04507P | 9 | | | ALL | |
| 201Z | | | IA | 0-0 | 22-14-11 | D05255J | | | FA | D04507P | | | FB | ALL | |
| 202B | 24 | PL | IB | 29-0 | 22-31-12 | D05259J | 4 | | | D05255J | 4 | | | ALL | |
| 202R | 24 | PL | IB | 0-0 | 22-31-12 | D05259J | 3 | | | D05255J | 3 | | | ALL | |
| 203B | 22 | PB | IC | 29-0 | 22-31-12 | D05259J | 6 | | | D05255J | 6 | | | ALL | |
| 203R | 22 | PB | IC | 0-0 | 22-31-12 | D05259J | 5 | | | D05255J | 5 | | | ALL | |
| 205 | 20 | UA | | 1-6 | 22-32-11 | D05255J | | | IE | GD00401 | S.. | 2 | | ALL | |
| 205B | 24 | PW | IE | 29-0 | 22-32-11 | D05259J | 14 | | | D05255J | 14 | | | ALL | |
| 205R | 24 | PW | IE | 0-0 | 22-32-11 | D05259J | 13 | | | D05255J | 13 | | | ALL | |
| 205Z | | | IE | 0-0 | 22-32-11 | D05259J | 9 | | | D05255J | | | IE | ALL | |
| 206B | 24 | PW | IF | 29-0 | 22-32-12 | D05259J | 16 | | | D05255J | 16 | | | ALL | |
| 206R | 24 | PW | IF | 0-0 | 22-32-12 | D05259J | 15 | | | D05255J | 15 | | | ALL | |
| 206Z | | | IF | 0-0 | 22-32-12 | D05259J | 17 | | | D05255J | 17 | | | ALL | |
| 208B | 22 | PR | IH | 29-0 | SPARE | D05259J | 19 | | | D05255J | 29 | | | ALL | |
| 208R | 22 | PR | IH | 0-0 | SPARE | D05259J | 18 | | | D05255J | 28 | | | ALL | |
| 208Z | | | IH | 0-0 | SPARE | D05259J | 20 | | | D05255J | 30 | | | ALL | |
| 209B | 24 | PL | II | 29-0 | 22-31-12 | D05255J | 8 | | | D05259J | 8 | | | ALL | |
| 209R | 24 | PL | II | 0-0 | 22-31-12 | D05255J | 7 | | | D05259J | 7 | | | ALL | |
| 210B | 24 | PW | IJ | 32-0 | SPARE | D04445J | 5 | | | D05255J | 35 | | | ALL | |
| 210R | 24 | PW | IJ | 0-0 | SPARE | D04445J | 4 | | | D05255J | 34 | | | ALL | |
| 210Z | | | IJ | 0-0 | SPARE | D04445J | 6 | | | D05255J | 36 | | | ALL | |
| 214 | 20 | UA | | 3-0 | 27-32-11 | D04507P | | | IN | GD00301 | S.. | 2 | | ALL | |
| 214B | 24 | PW | IN | 28-0 | 27-32-11 | D04507P | 12 | | | D05259J | 31 | | | ALL | |
| 214R | 24 | PW | IN | 0-0 | 27-32-11 | D04507P | 11 | | | D05259J | 30 | | | ALL | |
| 214Z | | | IN | 0-0 | 27-32-11 | D04507P | | | IN | D05259J | 26 | | | ALL | |
| 215 | 20 | UA | | 1-6 | 31-31-20 | D05255J | | | IO | GD00401 | S.. | 2 | | ALL | |
| 215B | 24 | PW | IO | 32-0 | 31-31-20 | D05255J | 11 | | | D04445J | 13 | | | ALL | |
| 215R | 24 | PW | IO | 0-0 | 31-31-20 | D05255J | 10 | | | D04445J | 12 | | | ALL | |
| 215Z | | | IO | 0-0 | 31-31-20 | D05255J | | | IO | D04445J | 14 | | | ALL | |
| 216 | 20 | UA | | 1-6 | 34-22-81 | D05255J | REF | | IP | GD00401 | S.. | 2 | | 157, 167-199, 277-299 | |
| 216 | 20 | UA | | 8-0 | 34-22-81 | D05255J | REF | | IP | GD00401 | S.. | 2 | | 275-276 | |
| 216B | 24 | PW | IP | 32-0 | 34-22-81 | D05255J | 51 | | | D04445J | 19 | | | 157, 167-199, 277-299 | |
| 216B | 24 | PW | IP | 37-0 | 34-22-81 | D05255J | 51 | | | D04445J | 19 | | | 275-276 | |
| 216R | 24 | PW | IP | 0-0 | 34-22-81 | D05255J | 50 | | | D04445J | 18 | | | 157, 167-199, 275-299 | |
| 216Z | | | IP | 0-0 | 34-22-81 | D05255J | REF | | IP | D04445J | 20 | | | 157, 167-199, 275-299 | |
| FRA | | | | 0-0 | 22-14-11 | D05255J | | | FA | D05255J | 41 | | | ALL | |
| FRE | | | | 0-0 | 22-32-11 | D05255J | | | IE | D05255J | 9 | | | ALL | |
| FRO | | | | 0-0 | 31-31-20 | D05255J | | | IO | D05255J | 12 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1310

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|--|-------|----------|-------------|------|------|-----------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1311 | 286T1311 | | | TMC,ALT ALERT & GWPS FWD PNL'S TO SHELVES & P51 (continued) | | | | | | | | | | | |
| FRP | | | | | 0-0 | 34-22-81 | D05255J | REF | | IP | D05255J | 52 | | | 157, 167-199, 275-299 |
| FRY | | | | | 0-0 | 34-45-14 | D05255J | 48 | | | D05255J | | | HY | 050-099, 150-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W1310
Page 3 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--------|------|------|--------|-------|------|---------|--------|-------------|----|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1328 | 286T1328 | | | | HYD MTR DR GEN DC PWR & CONTROL STD OPT 24-21 | | | | | | | | | | | | | |
| 001 | 20 | | UA | | 9-1 | 24-25-11 | D10834 | | 2 | | | | D06464P | | 1 | | | ALL |
| 002 | 20 | | UA | | 9-1 | 24-25-11 | D10834 | | 1 | | | | D06464P | | 2 | | | ALL |
| 003 | 20 | | UA | | 9-1 | 24-25-11 | D10834 | | 3 | | | | D06464P | | 3 | | | ALL |
| 004 | 20 | | UA | | 10-2 | 24-25-12 | D10844 | | 4 | | | | D06464P | | 7 | | | ALL |
| 005 | 20 | | UA | | 10-7 | 24-25-12 | D10840 | | 6 | | | | D06464P | | 17 | | | ALL |
| 006 | 12 | | UA | | 10-8 | 24-25-12 | D10840 | | 18 | | | | D06466P | | 1 | | | ALL |
| 007 | 12 | | UA | | 10-8 | 24-25-12 | D10840 | | 16 | | | | D06466P | | 2 | | | ALL |
| 008 | 12 | | UA | | 10-8 | 24-25-12 | D10840 | | 20 | | | | D06466P | | 3 | | | ALL |
| 009 | 12 | | UA | | 10-8 | 24-25-12 | D10840 | | 22 | | | | D06466P | | 4 | | | ALL |
| 010 | 20 | | UA | | 9-1 | 24-25-13 | D10834 | | 9 | | | | D06464P | | 14 | | | ALL |
| 012 | 20 | | UA | | 9-1 | 24-25-13 | D10834 | | 8 | | | | D06464P | | 16 | | | ALL |
| 201B | 20 | | VG | A | 10-7 | 24-25-12 | D10840 | | 4 | | | | D06464P | | 12 | | | ALL |
| 201R | 20 | | VG | A | 0-0 | 24-25-12 | D10840 | | 5 | | | | D06464P | | 13 | | | ALL |
| 201Z | | | | A | 0-0 | 24-25-12 | D10840 | | 7 | DL | | | D06464P | | 11 | DK | | ALL |
| 301B | 20 | | UC | B | 10-2 | 24-25-12 | D10844 | | 1 | | | | D06464P | | 4 | | | ALL |
| 301R | 20 | | UC | B | 0-0 | 24-25-12 | D10844 | | 2 | | | | D06464P | | 5 | | | ALL |
| 301Y | 20 | | UC | B | 0-0 | 24-25-12 | D10844 | | 3 | | | | D06464P | | 6 | | | ALL |
| 302B | 20 | | UC | C | 10-7 | 24-25-12 | D10840 | | 2 | | | | D06464P | | 8 | | | ALL |
| 302R | 20 | | UC | C | 0-0 | 24-25-12 | D10840 | | 1 | | | | D06464P | | 9 | | | ALL |
| 302Y | 20 | | UC | C | 0-0 | 24-25-12 | D10840 | | 3 | | | | D06464P | | 10 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1320
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1330 | 286T1330 | | | HYD MTR DR GEN AC PWR STD OPT 24-21 | | | | | | | | | | | | |
| 001 | 12 | | UA | 10-5 | 24-25-12 | D06468P | | 1 | | | | D10842 | | 1 | | ALL |
| 002 | 12 | | UA | 10-5 | 24-25-12 | D06468P | | 2 | | | | D10842 | | 2 | | ALL |
| 003 | 12 | | UA | 10-5 | 24-25-12 | D06468P | | 3 | | | | D10842 | | 3 | | ALL |
| 004 | 12 | | UA | 10-5 | 24-25-12 | D06468P | | 4 | | | | D10842 | | 4 | | ALL |
| W1332 | 286T1332 | | | HYD MOTOR DRIVEN GEN SYS CONTROL STD OPT 24-21 | | | | | | | | | | | | |
| 001 | 20 | | UA | 81-0 | 24-25-11 | D06464J | | 1 | | | | D06460P | | 1 | | 050-099, 150 |
| 001 | 20 | | UA | 91-0 | 24-25-11 | D06464J | | 1 | | | | D06460P | | 1 | | 151-199, 275-299 |
| 002 | 20 | | UA | 5-0 | 24-25-11 | D06464J | | 2 | | | | GD00668 | D.. | 2 | | ALL |
| 003 | 20 | | UA | 81-0 | 24-25-11 | D06464J | | 3 | | | | D06460P | | 2 | | 050-099, 150 |
| 003 | 20 | | UA | 91-0 | 24-25-11 | D06464J | | 3 | | | | D06460P | | 2 | | 151-199, 275-299 |
| 004 | 20 | | UA | 5-0 | 24-25-12 | D06464J | | 7 | | | | GD00668 | S.. | 2 | | ALL |
| 005 | 20 | | UA | 81-0 | 24-25-13 | D06464J | | 14 | | | | D06460P | | 12 | | 050-099, 150 |
| 005 | 20 | | UA | 91-0 | 24-25-13 | D06464J | | 14 | | | | D06460P | | 12 | | 151-199, 275-299 |
| 007 | 20 | | UA | 5-0 | 24-25-13 | D06464J | | 16 | | | | GD00668 | D.. | 2 | | ALL |
| 008 | 20 | | UA | 5-0 | 24-25-12 | D06464J | | 17 | | | | GD00668 | S.. | 2 | | ALL |
| 201B | 20 | | VG A | 81-0 | 24-25-12 | D06464J | | 12 | | | | D06460P | | 10 | | 050-099, 150 |
| 201B | 20 | | VG A | 91-0 | 24-25-12 | D06464J | | 12 | | | | D06460P | | 10 | | 151-199, 275-299 |
| 201R | 20 | | VG A | 0-0 | 24-25-12 | D06464J | | 13 | | | | D06460P | | 11 | | ALL |
| 201Z | | | A | 0-0 | 24-25-12 | D06464J | | 11 | DL | | | D06460P | | 9 | | ALL |
| 301B | 20 | | UC B | 81-0 | 24-25-12 | D06464J | | 4 | | | | D06460P | | 3 | | 050-099, 150 |
| 301B | 20 | | UC B | 91-0 | 24-25-12 | D06464J | | 4 | | | | D06460P | | 3 | | 151-199, 275-299 |
| 301R | 20 | | UC B | 0-0 | 24-25-12 | D06464J | | 5 | | | | D06460P | | 4 | | ALL |
| 301Y | 20 | | UC B | 0-0 | 24-25-12 | D06464J | | 6 | | | | D06460P | | 5 | | ALL |
| 302B | 20 | | UC C | 81-0 | 24-25-12 | D06464J | | 8 | | | | D06460P | | 6 | | 050-099, 150 |
| 302B | 20 | | UC C | 91-0 | 24-25-12 | D06464J | | 8 | | | | D06460P | | 6 | | 151-199, 275-299 |
| 302R | 20 | | UC C | 0-0 | 24-25-12 | D06464J | | 9 | | | | D06460P | | 7 | | ALL |
| 302Y | 20 | | UC C | 0-0 | 24-25-12 | D06464J | | 10 | | | | D06460P | | 8 | | ALL |
| 818 | 20 | | UA | 81-0 | SPARE | D06464J | | 18 | | | | D06460P | | 18 | | 050-099, 150 |
| 818 | 20 | | UA | 91-0 | SPARE | D06464J | | 18 | | | | D06460P | | 18 | | 151-199, 275-299 |
| 819 | 20 | | UA | 81-0 | SPARE | D06464J | | 19 | | | | D06460P | | 19 | | 050-099, 150 |
| 819 | 20 | | UA | 91-0 | SPARE | D06464J | | 19 | | | | D06460P | | 19 | | 151-199, 275-299 |
| 820 | 20 | | UA | 81-0 | SPARE | D06464J | | 20 | | | | D06460P | | 20 | | 050-099, 150 |
| 820 | 20 | | UA | 91-0 | SPARE | D06464J | | 20 | | | | D06460P | | 20 | | 151-199, 275-299 |
| 821 | 20 | | UA | 81-0 | SPARE | D06464J | | 21 | | | | D06460P | | 21 | | 050-099, 150 |
| 821 | 20 | | UA | 91-0 | SPARE | D06464J | | 21 | | | | D06460P | | 21 | | 151-199, 275-299 |
| W1334 | 286T1334 | | | HYD MOTOR DRIVEN GEN DC PWR STD OPT 24-21 | | | | | | | | | | | | |
| 001 | 12 | | UA | 5-0 | 24-25-12 | D06466J | | 1 | | | | GD04688 | D.. | E | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1330

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1334 | 286T1334 | | | HYD MOTOR DRIVEN GEN DC PWR STD OPT 24-21 (continued) | | | | | | | | | | | |
| 002 | 12 | | UA | | 5-0 | 24-25-12 | D06466J | | | | GD04688 | D.. | E | | ALL |
| 003 | 12 | | UA | | 4-0 | 24-25-12 | D06466J | | | | SM00001 | | 9 | | 050-099, 151-199, 275-299 |
| 003 | 12 | | UA | | 5-0 | 24-25-12 | D06466J | | | | SM00001 | | 9 | | 150 |
| 004 | 12 | | UA | | 4-0 | 24-25-12 | D06466J | | | | SM00001 | | 9 | | 050-099, 151-199, 275-299 |
| 004 | 12 | | UA | | 5-0 | 24-25-12 | D06466J | | | | SM00001 | | 9 | | 150 |
| 005 | 06 | | UA | | 80-0 | 24-25-12 | SM00001 | | | 9 | K00861 | A1 | F | | 050-099 |
| 005 | 06 | | UA | | 81-0 | 24-25-12 | SM00001 | | | 9 | K00861 | A1 | F | | 150 |
| 005 | 06 | | UA | | 90-0 | 24-25-12 | SM00001 | | | 9 | K00861 | A1 | F | | 151-199, 275-299 |
| W1336 | 286T1336 | | | HYD MOTOR DRIVEN GEN AC PWR STD OPT 24-21 | | | | | | | | | | | |
| 001 | 12 | | UA | | 82-0 | 24-25-12 | D06468J | | | | D06462P | | 1 | | 050-099 |
| 001 | 12 | | UA | | 81-0 | 24-25-12 | D06468J | | | | D06462P | | 1 | | 150 |
| 001 | 12 | | UA | | 92-0 | 24-25-12 | D06468J | | | | D06462P | | 1 | | 151-199, 275-299 |
| 002 | 12 | | UA | | 82-0 | 24-25-12 | D06468J | | | | D06462P | | 2 | | 050-099 |
| 002 | 12 | | UA | | 81-0 | 24-25-12 | D06468J | | | | D06462P | | 2 | | 150 |
| 002 | 12 | | UA | | 92-0 | 24-25-12 | D06468J | | | | D06462P | | 2 | | 151-199, 275-299 |
| 003 | 12 | | UA | | 82-0 | 24-25-12 | D06468J | | | | D06462P | | 3 | | 050-099 |
| 003 | 12 | | UA | | 81-0 | 24-25-12 | D06468J | | | | D06462P | | 3 | | 150 |
| 003 | 12 | | UA | | 92-0 | 24-25-12 | D06468J | | | | D06462P | | 3 | | 151-199, 275-299 |
| 004 | 12 | | UA | | 5-0 | 24-25-12 | D06468J | | | | GD04686 | A.. | E | | ALL |
| W1338 | 286T1338 | | | HYD MTR DR GEN DC PWR & CONROL STD OPT 24-21 | | | | | | | | | | | |
| 001 | 22 | | PA | | 27-0 | 24-25-11 | D06452P | | | | D06442P | | 2 | | ALL |
| 002 | 22 | | PA | | 27-0 | 24-25-11 | D06452P | | | | D06442P | | 4 | | ALL |
| 003 | 22 | | PA | | 27-0 | 24-25-11 | D06452P | | | | D06442P | | 5 | | ALL |
| 004 | 22 | | PA | | 27-0 | 24-25-11 | D06452P | | | | D06442P | | 6 | | ALL |
| 005 | 22 | | PA | | 27-0 | SPARE | D06452P | | | | D06442P | | 7 | | ALL |
| 006 | 22 | | PA | | 13-0 | 24-25-11 | D06452P | | | | D06470P | | 1 | | ALL |
| 007 | 22 | | PA | | 13-0 | 24-25-11 | D06452P | | | | D06470P | | 2 | | ALL |
| 010 | 24 | | PK | | 13-0 | 24-25-13 | D06452P | | | | D06470P | | 3 | | ALL |
| 011 | 24 | | PK | | 13-0 | 24-25-13 | D06452P | | | | D06470P | | 4 | | ALL |
| 012 | 24 | | PK | | 13-0 | 24-25-13 | D06452P | | | | D06470P | | 5 | | ALL |
| 013 | 24 | | PK | | 13-0 | 24-25-13 | D06452P | | | | D06470P | | 6 | | ALL |
| 014 | 22 | | PA | | 27-0 | 33-51-11 | D06452P | | | | D06442P | | 8 | | ALL |
| 015 | 22 | | PA | | 13-0 | 29-11-32 | D06452P | | | | D06470P | | 7 | | ALL |
| 016 | 06 | | HA | | 22-0 | 24-31-11 | TB5014 | | | G | K00861 | A2 | F | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W1330
 Page 2 End
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | |
|------------------------|-----------------|--|----|------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|----|-------------|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W1340 | 286T1340 | LEFT & INSTR BUS/HYD MTR DR GEN TRANSFER BUS AC PWR STD OPT 24-21 | | | | | | | | | | | | | | | | |
| 001 | 12 | | PA | 23-0 | 24-51-14 | D06444P | | 1 | | | | | D06454P | | 1 | | | ALL |
| 002 | 12 | | PA | 23-0 | 24-51-14 | D06444P | | 2 | | | | | D06454P | | 2 | | | ALL |
| 003 | 12 | | PA | 23-0 | 24-51-14 | D06444P | | 3 | | | | | D06454P | | 3 | | | ALL |
| 004 | 14 | | PA | 24-0 | 24-51-14 | D06448P | | 1 | | | | | D06456P | | 14 | | | ALL |
| 005 | 14 | | PA | 24-0 | 24-51-14 | D06448P | | 2 | | | | | D06456P | | 16 | | | ALL |
| 006 | 14 | | PA | 24-0 | 24-51-14 | D06448P | | 3 | | | | | D06456P | | 18 | | | ALL |
| 007 | 12 | | PA | 23-0 | 24-51-42 | D06444P | | 4 | | | | | D06454P | | 4 | | | ALL |
| 008 | 12 | | PA | 23-0 | 24-51-42 | D06444P | | 5 | | | | | D06454P | | 5 | | | ALL |
| 009 | 12 | | PA | 23-0 | 24-51-42 | D06444P | | 6 | | | | | D06454P | | 6 | | | ALL |
| 010 | 16 | | PA | 24-0 | 24-51-42 | D06448P | | 6 | | | | | D06456P | | 20 | | | ALL |
| 011 | 16 | | PA | 24-0 | 24-51-42 | D06448P | | 5 | | | | | D06456P | | 22 | | | ALL |
| 012 | 16 | | PA | 24-0 | 24-51-42 | D06448P | | 4 | | | | | D06456P | | 24 | | | ALL |
| 013 | 12 | | PA | 23-0 | SPARE | D06444P | | 7 | | | | | D06454P | | 7 | | | ALL |
| 014 | 22 | | PA | 12-0 | 34-22-81 | D06456P | | 7 | | | | | SP00373 | | | 9 | | ALL |
| W1342 | 286T1342 | RIGHT BUS/HYD MTR DR GEN TRANSFER BUS AC PWR STD OPT 24-21 | | | | | | | | | | | | | | | | |
| 001 | 12 | | PA | 34-0 | 24-51-24 | D06446P | | 1 | | | | | SP02756 | | 9 | | | ALL |
| 002 | 12 | | PA | 22-0 | 24-51-24 | D06446P | | 2 | | | | | SM00001 | | 9 | | | ALL |
| 003 | 12 | | PA | 26-0 | 24-51-24 | D06446P | | 3 | | | | | D06458P | | 3 | | | ALL |
| 004 | 18 | | PA | 22-0 | 24-51-24 | D06450P | | 1 | | | | | D06474P | | 1 | | | ALL |
| 005 | 18 | | PA | 22-0 | 24-51-24 | D06450P | | 2 | | | | | D06474P | | 2 | | | ALL |
| 006 | 18 | | PA | 22-0 | 24-51-24 | D06450P | | 3 | | | | | D06474P | | 3 | | | ALL |
| 007 | 12 | | PA | 18-0 | 24-51-24 | D06458P | | 1 | | | | | SP02756 | | 9 | | | ALL |
| 008 | 12 | | PA | 6-0 | 24-51-24 | D06458P | | 2 | | | | | SM00001 | | 9 | | | ALL |
| 009 | 12 | | PA | 15-0 | 24-51-24 | D06476P | | 1 | | | | | SM00001 | | 9 | | | ALL |
| 010 | 12 | | PA | 26-0 | SPARE | D06458P | | 4 | | | | | D06446P | | 4 | | | ALL |
| W1343 | 286T1343 | SERVICE INTERPHONE | | | | | | | | | | | | | | | | |
| 001 | 22 | | PA | 26-0 | 23-43-11 | D04613J | | 7 | | | | | B00060 | =P | L | | | ALL |
| 002 | 20 | | PA | 26-0 | 23-43-11 | D04613J | | 8 | | | | | B00060 | =G | L | | | ALL |
| 201B | 24 | | PW | IA | 15-0 | 23-41-11 | SM00008 | | | | VL | | D04613J | | 2 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 23-41-11 | SM00007 | | | | VL | | D04613J | | 1 | | | ALL |
| 201Z | | | | IA | 0-0 | 23-41-11 | SM00008 | REF | | | VL | FA | D04613J | | 3 | | | ALL |
| 202B | 24 | | PW | IB | 6-0 | 23-41-11 | SM00008 | | | | VL | | SP00169 | | 9 | | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 23-41-11 | SM00007 | | | | VL | | SP00167 | | 9 | | | ALL |
| 202Z | | | | IB | 0-0 | 23-41-11 | SM00008 | REF | | | VL | FA | SP00171 | | 9 | | | ALL |
| 204B | 24 | | PW | ID | 19-0 | 23-41-11 | SM00008 | | | | VL | | SM00002 | | 9 | | | ALL |
| 204R | 24 | | PW | ID | 0-0 | 23-41-11 | SM00007 | | | | VL | | SM00001 | | 9 | | | ALL |
| 204Z | | | | ID | 0-0 | 23-41-11 | SM00008 | REF | | | VL | FA | SM00003 | | 9 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1340

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | To | | | | |
|--------------|-----------------|-------------|----|---------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1343 | 286T1343 | | | SERVICE INTERPHONE (continued) | | | | | | | | | | | |
| 205B | 24 | PW | IE | | 27-0 | 23-41-11 | SM00008 | | VL | | SM00005 | | 9 | | ALL |
| 205R | 24 | PW | IE | | 0-0 | 23-41-11 | SM00007 | | VL | | SM00004 | | 9 | | ALL |
| 205Z | | | IE | | 0-0 | 23-41-11 | SM00008 | REF | VL | FA | SM00006 | | 9 | | ALL |
| 206B | 24 | PW | IF | | 56-0 | 23-41-11 | D04613J | | 5 | | SP00163 | | S | | ALL |
| 206R | 24 | PW | IF | | 0-0 | 23-41-11 | D04613J | | 4 | | SP00161 | | S | | ALL |
| 206Z | | | IF | | 0-0 | 23-41-11 | D04613J | | 6 | | SP00165 | | S | | ALL |
| 207B | 24 | PW | IG | | 61-0 | 23-41-11 | SM00013 | | VL | | SP00163 | | S | | ALL |
| 207R | 24 | PW | IG | | 0-0 | 23-41-11 | SM00012 | | VL | | SP00161 | | S | | ALL |
| 207Z | | | IG | | 0-0 | 23-41-11 | SM00013 | REF | VL | FB | SP00165 | | S | | ALL |
| 208B | 24 | PW | IH | | 13-0 | 23-41-11 | SM00013 | | VL | | SP00187 | | S | | 050-099 |
| 208B | 24 | PW | IH | | 24-0 | 23-41-11 | SM00013 | | VL | | SP00187 | | S | | 150-199, 275-299 |
| 208R | 24 | PW | IH | | 0-0 | 23-41-11 | SM00012 | | VL | | SP00185 | | S | | ALL |
| 208Z | | | IH | | 0-0 | 23-41-11 | SM00013 | REF | VL | FB | SP00189 | | S | | ALL |
| 209B | 24 | PW | II | | 43-0 | 23-41-11 | SM00013 | | VL | | D05409J | 2 | | | ALL |
| 209R | 24 | PW | II | | 0-0 | 23-41-11 | SM00012 | | VL | | D05409J | 1 | | | ALL |
| 209Z | | | II | | 0-0 | 23-41-11 | SM00013 | REF | VL | FB | D05409J | 3 | | | ALL |
| A-A | | | A | | 0-0 | 23-41-11 | D08539 | | RED | | SM00001 | | 9 | | ALL |
| A-B | | | A | | 0-0 | 23-41-11 | D08539 | | BLU | | SM00002 | | 9 | | ALL |
| A-C | | | A | | 0-0 | 23-41-11 | D08539 | | BLK | | SM00003 | | 9 | | ALL |
| A-D | | | B | | 0-0 | 23-41-11 | D08541 | | RED | | SM00004 | | 9 | | ALL |
| A-E | | | B | | 0-0 | 23-41-11 | D08541 | | BLU | | SM00005 | | 9 | | ALL |
| A-F | | | B | | 0-0 | 23-41-11 | D08541 | | BLK | | SM00006 | | 9 | | ALL |
| W1349 | 286T1349 | | | ELEC SPOILER CONT | | | | | | | | | | | |
| WBK | 18 | 7M | 1D | | 2-9 | 27-61-18 | D05459P | | 8 | | D00161 | | 8 | | ALL |
| WBN | 18 | 7M | 1C | | 0-0 | 27-61-18 | D05459P | | 6 | | D00161 | | 6 | | ALL |
| WBU | 18 | 7M | 1A | | 0-0 | 27-61-18 | D05459P | | 2 | | D00161 | | 2 | | ALL |
| WGR | 18 | 7M | 1B | | 0-0 | 27-61-18 | D05459P | | 4 | | D00161 | | 4 | | ALL |
| WOB | 18 | 7M | 1E | | 0-0 | 27-61-18 | D05459P | | 10 | | D00161 | | 10 | | ALL |
| WOR | 18 | 7M | 1C | | 0-0 | 27-61-18 | D05459P | | 5 | | D00161 | | 5 | | ALL |
| WRB | 18 | 7M | 1C | | 0-0 | 27-61-18 | D05459P | | 7 | | D00161 | | 7 | | ALL |
| WRD | 18 | 7M | 1A | | 0-0 | 27-61-18 | D05459P | | 1 | | D00161 | | 1 | | ALL |
| WVI | 18 | 7M | 1D | | 0-0 | 27-61-18 | D05459P | | 9 | | D00161 | | 9 | | ALL |
| WYL | 18 | 7M | 1B | | 0-0 | 27-61-18 | D05459P | | 3 | | D00161 | | 3 | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1354 | 286T1354 | | | WIRING FROM STA 1535 PRODUCTION BRK TO LOWER SEC 46 EQUIPMENT | | | | | | | | | | | | | | |
| 001 | 16 | | PA | 15-0 | 21-26-11 | D06314J | | 14 | | | | | D00456 | | 6 | | | ALL |
| 002 | 16 | | PA | 15-0 | 21-26-11 | D06314J | | 16 | | | | | D00456 | | 4 | | | ALL |
| 003 | 16 | | PA | 15-0 | 21-26-11 | D06314J | | 18 | | | | | D00456 | | 7 | | | ALL |
| 004 | 24 | | PV | 15-0 | 21-26-11 | D06314J | | 1 | | | | | D00456 | | 2 | | | ALL |
| 004Z | | | | 0-0 | 21-26-11 | D06314J | | DED | | | | | D00456 | DED | | | | ALL |
| 005 | 20 | | PQ | 5-0 | 21-26-11 | D00456 | | 3 | | | | | GD01338 | D.. | E | | | ALL |
| 005Z | | | | 0-0 | 21-26-11 | D00456 | | DED | | | | | GD01338 | DED | | | | ALL |
| 006 | 16 | | PA | 4-0 | 21-26-11 | D00456 | | 1 | | | | | GD01340 | S.. | E | | | ALL |
| 007 | 20 | | PA | 36-0 | 38-32-11 | SP00268 | | | 9 | | | | D01262 | | 3 | | | 050-099, 150-155, 162-165 |
| 007 | 20 | | PA | 40-0 | 38-32-15 | SP05436 | | | 9 | | | | D01262 | | 3 | | | 156, 166 |
| 007 | 20 | | PA | 22-0 | 38-32-15 | SP05436 | | | 9 | | | | D01262 | | 3 | | | 157, 167-199, 277-299 |
| 007 | 20 | | PA | 22-0 | 38-32-14 | SP00268 | | | 9 | | | | SM00009 | | 9 | | | 275-276 |
| 009 | 20 | | PA | 12-0 | 38-32-11 | D06314J | | 15 | | | | | D01262 | | 4 | | | 050-099, 155-199, 277-299 |
| 010 | 20 | | PA | 8-0 | 21-31-11 | D06314J | | 5 | | | | | D03196 | | 6 | | | ALL |
| 011 | 20 | | PA | 5-0 | 21-31-11 | D03196 | | 7 | | | | | GD04708 | A.. | E | | | ALL |
| 012 | 20 | | PA | 5-0 | 21-31-11 | D03196 | | 3 | | | | | GD04708 | A.. | E | | | ALL |
| 013 | 20 | | PA | 5-0 | 21-31-11 | D03196 | | 2 | | | | | GD04712 | S.. | E | | | ALL |
| 014 | 20 | | UA | 5-0 | 21-31-11 | GD04712 | | S.. | E | | | | D03196 | | | FA | | ALL |
| 015 | 22 | | PA | 14-0 | 38-32-11 | D06314J | | 8 | | | | | SP01634 | | 9 | | | 050-099, 275-299 |
| 015 | 20 | | PA | 14-0 | 38-32-11 | D06314J | | 8 | | | | | SP01634 | | 9 | | | 150-199 |
| 016 | 12 | | PA | 15-0 | 38-32-11 | D06314J | | 20 | | | | | D01266 | | 4 | | | ALL |
| 017 | 12 | | PA | 15-0 | 38-32-11 | D06314J | | 22 | | | | | D01266 | | 3 | | | ALL |
| 018 | 12 | | PA | 15-0 | 38-32-11 | D06314J | | 24 | | | | | D01266 | | 2 | | | ALL |
| 019 | 22 | | PA | 15-0 | 38-32-11 | D06314J | | 9 | | | | | SM00005 | | 9 | | | 050-099, 275-299 |
| 019 | 20 | | PA | 15-0 | 38-32-11 | D06314J | | 9 | | | | | SM00005 | | 9 | | | 150-199 |
| 020 | 22 | | PA | 12-0 | 38-32-11 | D06314J | | 10 | | | | | D01262 | | 2 | | | 050-099, 275-276 |
| 020 | 20 | | PA | 12-0 | 38-32-11 | D06314J | | 10 | | | | | D01262 | | 2 | | | 150-156, 162-165 |
| 020 | 18 | | PA | 12-0 | 38-32-11 | D06314J | | 10 | DL | | | | D01262 | | 2 | DK | | 157, 166-199, 277-299 |
| 021 | 22 | | PA | 25-0 | 38-32-11 | D06314J | | 11 | | | | | SP00550 | | 9 | | | 050-099, 275-276 |
| 021 | 20 | | PA | 25-0 | 38-32-11 | D06314J | | 11 | | | | | SP00550 | | 9 | | | 150-156, 162-165 |
| 021 | 18 | | PA | 25-0 | 38-32-11 | D06314J | | 11 | DL | | | | SP00550 | | 9 | | | 157, 166-199, 277-299 |
| 022 | 22 | | PA | 22-0 | 38-32-11 | D01262 | | 1 | | | | | SP00550 | | 9 | | | 050-099, 275-276 |
| 022 | 20 | | PA | 22-0 | 38-32-11 | D01262 | | 1 | | | | | SP00550 | | 9 | | | 150-156, 162-165 |
| 022 | 18 | | PA | 22-0 | 38-32-11 | D01262 | | 1 | DK | | | | SP00550 | | 9 | | | 157, 166-199, 277-299 |
| 023 | 22 | | PA | 28-0 | 38-32-11 | D01262 | | 6 | | | | | SP00550 | | 9 | | | 050-099, 275-276 |
| 023 | 20 | | PA | 28-0 | 38-32-11 | D01262 | | 6 | | | | | SP00550 | | 9 | | | 150-156, 162-165 |
| 023 | 18 | | PA | 27-5 | 38-32-11 | D01262 | | 6 | DK | | | | SP00550 | | 9 | | | 157, 166-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W1350

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1354 | 286T1354 | | | WIRING FROM STA 1535 PRODUCTION BRK TO LOWER SEC 46 EQUIPMENT (continued) | | | | | | | | | | | |
| 024 | 22 | | PA | | 22-0 | 38-32-11 | D01262 | | | | SP01624 | | | | 050-099, 275-299 |
| 024 | 20 | | PA | | 22-0 | 38-32-11 | D01262 | | | | SP01624 | | | | 150-199 |
| 025 | 22 | | PA | | 22-0 | 38-32-11 | D01262 | | | | SP01626 | | | | 050-099, 275-299 |
| 025 | 20 | | PA | | 22-0 | 38-32-11 | D01262 | | | | SP01626 | | | | 150-199 |
| 026 | 20 | | PA | | 5-0 | 38-32-11 | D01262 | | | | GD03248 | S.. | E | | ALL |
| 027 | 20 | | PA | | 5-0 | 38-32-11 | D01262 | | | | GD03246 | D.. | E | | ALL |
| 028 | 18 | | PA | | 8-10 | 38-32-11 | D01266 | | | | SP01816 | | | | ALL |
| 029 | 18 | | PA | | 1-0 | 38-32-11 | D01266 | | | | SM00005 | | | | ALL |
| 030 | 12 | | PA | | 8-0 | 38-32-11 | D01266 | | | | GD03248 | S.. | E | | ALL |
| 033 | 20 | | PA | | 7-0 | 38-32-11 | D01262 | | | | GD03246 | D.. | E | | 050-099, 155, 162-165 |
| 041 | 20 | | PA | | 9-0 | 38-32-14 | GD03246 | | D.. | E | D11968 | | | 1 | 050-099, 150-199, 277-299 |
| 042 | 20 | | PA | | 9-0 | 38-32-14 | GD03248 | | S.. | E | D11968 | | | 2 | 050-099, 150-199, 277-299 |
| 043 | 22 | | PA | | 22-0 | 38-32-11 | D01262 | | | | SP03986 | | | S | 156-157, 166-199 |
| 043 | 22 | | PA | | 22-0 | 38-32-11 | D01262 | | | | SP03986 | | | 9 | 275-299 |
| 044 | 18 | | PA | | 18-0 | 38-32-14 | D06314J | | | DL | D11968 | 4 | DK | | 050-099, 150-154 |
| 044 | 18 | | PA | | 18-0 | 38-32-14 | D06314J | | | DL | D01262 | 3 | DK | | 275-276 |
| 045 | 18 | | PA | | 18-0 | 38-32-14 | D06314J | | | DL | D11968 | 5 | DK | | 050-099, 150-199, 277-299 |
| 045 | 18 | | PA | | 18-0 | 38-32-14 | D06314J | | 13 | DL | SM00009 | | | 9 | 275-276 |
| 046 | 22 | | PA | | 30-0 | 38-32-11 | SP00268 | | | | SP04040 | | | 9 | 050, 150-154 |
| 046 | 22 | | PA | | 26-0 | 38-32-11 | SP00268 | | | | SP04040 | | | 9 | 051-099, 155, 162-165 |
| 046 | 22 | | PA | | 26-0 | 38-32-15 | SP00268 | | | | SP04040 | | | 9 | 156-157, 166-199, 277-299 |
| 046 | 22 | | PA | | 30-0 | 38-32-14 | SP00268 | | | | SP04040 | | | 9 | 275-276 |
| 047 | 22 | | PA | | 30-0 | 38-32-11 | SP00550 | | | | SP04042 | | | 9 | 050, 150-154 |
| 047 | 22 | | PA | | 25-0 | 38-32-11 | SP00550 | | | | SP04042 | | | 9 | 051-099, 155, 162-165 |
| 047 | 22 | | PA | | 25-0 | 38-32-15 | SP00550 | | | | SP04042 | | | 9 | 156-157, 166-199, 277-299 |
| 047 | 22 | | PA | | 30-0 | 38-32-14 | SP00550 | | | | SP04042 | | | 9 | 275-276 |
| 048 | 20 | | PA | | 20-0 | 38-32-11 | GD01338 | | D.. | E | SP04044 | | | 9 | 050, 150-154 |
| 048 | 20 | | PA | | 14-0 | 38-32-11 | GD01338 | | D.. | E | SP04044 | | | 9 | 051-099, 155, 162-165 |
| 048 | 20 | | PA | | 14-0 | 38-32-15 | GD01338 | | D.. | E | SP04044 | | | 9 | 156-157, 166-199, 277-299 |
| 048 | 20 | | PA | | 18-0 | 38-32-14 | GD01338 | | D.. | E | SP04044 | | | 9 | 275-276 |
| 052 | 22 | | PA | | 25-0 | 38-32-14 | D01262 | | | 4 | SP05402 | | | 9 | 275-276 |
| 056 | 20 | | PA | | 22-0 | 38-32-11 | SP03636 | | | | D01262 | | CAP | Y | 050-099, 150-155, 162-165 |

WIRE LIST
D280T132

91-21-11
Section W1350
Page 2
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|--|-------------|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1354 | 286T1354 | | | WIRING FROM STA 1535 PRODUCTION BRK TO LOWER SEC 46 EQUIPMENT (continued) | | | | | | | | | | | | | |
| 056 | 20 | | PA | 22-0 | 38-32-11 | SP03636 | | | | 9 | | | D01262 | 18 | | | 156-157, 166-199, 275-299 |
| 201B | 24 | | PW | C | 8-0 | 21-31-11 | D06314J | | | 2 | | | D03196 | 10 | | | ALL |
| 201R | 24 | | PW | C | 0-0 | 21-31-11 | D06314J | | | 3 | | | D03196 | 9 | | | ALL |
| 201Z | | | | C | 0-0 | 21-31-11 | D06314J | | | 4 | | | D03196 | | | FA | ALL |
| 202B | 20 | | PB | D | 8-0 | 21-31-11 | D06314J | | | 6 | | | D03196 | 1 | | | ALL |
| 202R | 20 | | PB | D | 0-0 | 21-31-11 | D06314J | | | 7 | | | D03196 | 5 | | | ALL |
| A-A | | | | | 0-0 | 38-32-11 | S00352 | | BLU | | | | SP01634 | 9 | | | ALL |
| A-B | | | | | 0-0 | 38-32-11 | S00352 | | RED | | | | SP01632 | 9 | | | ALL |
| A-F | | | | | 0-0 | 38-32-11 | SP04040 | | | 9 | | | L01205 | RED | | | 050-099, 150-155, 162-165 |
| A-F | | | | | 0-0 | 38-32-15 | SP04040 | | | 9 | | | L01205 | RED | | | 156-157, 166-199, 277-299 |
| A-F | | | | | 0-0 | 38-32-14 | SP04040 | | | 9 | | | L01205 | RED | | | 275-276 |
| A-G | | | | | 0-0 | 38-32-11 | SP04042 | | | 9 | | | L01205 | WHT | | | 050-099, 150-155, 162-165 |
| A-G | | | | | 0-0 | 38-32-15 | SP04042 | | | 9 | | | L01205 | WHT | | | 156-157, 166-199, 277-299 |
| A-G | | | | | 0-0 | 38-32-14 | SP04042 | | | 9 | | | L01205 | WHT | | | 275-276 |
| A-H | | | | | 0-0 | 38-32-11 | SP04044 | | | 9 | | | L01205 | BLK | | | 050-099, 150-155, 162-165 |
| A-H | | | | | 0-0 | 38-32-15 | SP04044 | | | 9 | | | L01205 | BLK | | | 156-157, 166-199, 277-299 |
| A-H | | | | | 0-0 | 38-32-14 | SP04044 | | | 9 | | | L01205 | BLK | | | 275-276 |
| W1356 | 286T1356 | | | AFT WATER SUPPLY LINE & DRAIN LINE HEATERS | | | | | | | | | | | | | |
| 001 | 16 | | PA | 11-7 | 30-71-24 | D06304J | | | 12 | FL | | | SP03384 | 9 | | | 050-099, 150-199 |
| 002 | 20 | | PA | 28-10 | 30-71-23 | D06304J | | | 2 | | | | SP00322 | 9 | | | 050-099, 155-199 |
| 002 | 22 | | PA | 28-10 | 30-71-23 | D06304J | | | 2 | | | | SP00322 | 9 | | | 150-154, 275-299 |
| 003 | 20 | | PA | 19-11 | 30-71-24 | D06304J | | | 3 | | | | SP00628 | 9 | | | 050-099 |
| 003 | 22 | | PA | 19-11 | 30-71-23 | D06304J | | | 3 | | | | SP00628 | 9 | | | 150-154, 277-299 |
| 003 | 20 | | PA | 19-11 | 30-71-23 | D06304J | | | 3 | | | | SP00628 | 9 | | | 155-199 |
| 004 | 20 | | PA | 19-11 | 30-71-24 | D06304J | | | 4 | | | | SP00358 | 9 | | | 050-099 |
| 004 | 22 | | PA | 19-11 | 30-71-23 | D06304J | | | 4 | | | | SP00358 | 9 | | | 150-154, 275-299 |
| 004 | 20 | | PA | 19-11 | 30-71-23 | D06304J | | | 4 | | | | SP00358 | 9 | | | 155-199 |
| 005 | 20 | | PA | 18-11 | 30-71-23 | D06304J | | | 5 | | | | SP00324 | 9 | | | 050-099 |
| 005 | 20 | | PA | 18-11 | 30-71-24 | D06304J | | | 5 | | | | SP03382 | 9 | | | 150-199 |
| 006 | 20 | | PA | 21-7 | 30-71-24 | D06304J | | | 6 | | | | SP00318 | 9 | | | 050-099 |
| 006 | 22 | | PA | 21-7 | 30-71-23 | D06304J | | | 6 | | | | SP00318 | 9 | | | 150-154, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1350

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1356 | 286T1356 | | | AFT WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | |
| 006 | 20 | | PA | | 21-7 | 30-71-23 | D06304J | | 6 | | SP00318 | | 9 | | 155-199 |
| 015 | 16 | | PA | | 9-2 | 30-71-24 | SP03387 | | | 9 | GD05538 | A.. | 2 | | 050-099, 150-199 |
| 018 | 24 | | PK | | 16-6 | 38-15-11 | D06304J | | 18 | | D01290 | | 2 | | 050-099, 275-299 |
| 018 | 24 | | PK | | 16-6 | 38-15-11 | D06304J | | 7 | | D01290 | | 2 | | 150-199 |
| 019 | 24 | | PK | | 14-4 | 21-44-21 | D06304J | | 19 | | D00504 | | 1 | | 050-099, 275-299 |
| 019 | 24 | | PK | | 14-4 | 21-44-21 | D06304J | | 8 | | D00504 | | 1 | | 150-199 |
| 020 | 24 | | PK | | 14-4 | 21-44-21 | D06304J | | 20 | | D00524 | | 1 | | 050-099, 275-299 |
| 020 | 24 | | PK | | 14-4 | 21-44-21 | D06304J | | 9 | | D00524 | | 1 | | 150-199 |
| 022 | 20 | | PA | | 13-11 | 30-71-23 | D06304J | | 10 | | SP02708 | | 9 | | 050-099, 155-199 |
| 022 | 22 | | PA | | 13-11 | 30-71-23 | D06304J | | 10 | | SP02708 | | 9 | | 150-154 |
| 022 | 22 | | PA | | 13-11 | 30-71-23 | D06304J | | 22 | | SP02708 | | 9 | | 275-299 |
| 023 | 20 | | PA | | 16-0 | 30-71-23 | D06304J | | 11 | | SP02718 | | 9 | | 050-099, 155-199 |
| 023 | 22 | | PA | | 16-0 | 30-71-23 | D06304J | | 11 | | SP02718 | | 9 | | 150-154 |
| 023 | 22 | | PA | | 16-0 | 30-71-23 | D06304J | | 23 | | SP02718 | | 9 | | 275-299 |
| 025 | 20 | | PA | | 19-11 | 30-71-24 | D06304J | | 1 | | SP00442 | | 9 | | 050-099 |
| 025 | 22 | | PA | | 19-11 | 30-71-23 | D06304J | | 1 | | SP00442 | | 9 | | 150-154 |
| 025 | 20 | | PA | | 19-11 | 30-71-23 | D06304J | | 1 | | SP00442 | | 9 | | 155-199 |
| 026 | 20 | | PA | | 4-7 | 30-71-24 | GD04382 | A.. | E | | SP00444 | | 9 | | 050-099 |
| 026 | 20 | | PA | | 4-7 | 30-71-23 | SP00444 | | 9 | | GD04382 | A.. | E | | 150-199 |
| 03X | 20 | | PA | | 4-7 | 30-71-24 | SP00354 | | 9 | | GD04382 | A.. | E | | 050-099 |
| 03X | 20 | | PA | | 4-7 | 30-71-23 | SP00354 | | 9 | | GD04382 | A.. | E | | 150-199, 277-299 |
| 18C | 24 | | PK | | 7-2 | 38-15-11 | SP01960 | | 9 | | D01290 | | 3 | | ALL |
| 19B | 20 | | PA | | 3-6 | 21-44-21 | GD03564 | D.. | E | | D00504 | | 2 | | ALL |
| 20B | 20 | | PA | | 3-6 | 21-44-21 | GD03564 | D.. | E | | D00524 | | 2 | | ALL |
| 22X | 20 | | PA | | 7-2 | 30-71-23 | SP02750 | | 9 | | GD00066 | A.. | 2 | | ALL |
| 23X | 20 | | PA | | 6-3 | 30-71-23 | SP02726 | | 9 | | GD04586 | A.. | E | | ALL |
| 553 | 20 | | PA | | 46-9 | 38-15-11 | SP01958 | | 9 | | SP00594 | | 9 | | 050-099, 150-199 |
| 553 | 20 | | PA | | 6-5 | 38-15-11 | SP01958 | | 9 | | GD00066 | D.. | 2 | | 275-299 |
| 55X | 20 | | PA | | 10-10 | 38-15-11 | GD00070 | D.. | 2 | | SP00596 | | 9 | | 050-099, 150-199 |
| A-A | | | | | 0-0 | 30-71-23 | B00212 | | =P | | SP00322 | | 9 | | ALL |
| A-B | | | | | 0-0 | 30-71-23 | B00212 | | =G | | GD00976 | A.. | E | | ALL |
| A-C | | | | | 0-0 | 30-71-23 | B00213 | | =P | | SP00322 | | 9 | | ALL |
| A-D | | | | | 0-0 | 30-71-23 | B00213 | | =G | | GD00976 | A.. | E | | ALL |
| A-E | | | | | 0-0 | 30-71-24 | B00110 | | =P | | SP00442 | | 9 | | 050-099 |
| A-E | | | | | 0-0 | 30-71-23 | B00110 | | =P | | SP00442 | | 9 | | 150-199 |
| A-F | | | | | 0-0 | 30-71-24 | B00110 | | =G | | SP00444 | | 9 | | 050-099 |
| A-F | | | | | 0-0 | 30-71-23 | B00110 | | =G | | SP00444 | | 9 | | 150-199 |
| B-A | | | | | 0-0 | 30-71-24 | B00100 | | =P | | SP00318 | | 9 | | 050-099 |
| B-A | | | | | 0-0 | 30-71-23 | B00100 | | =P | | SP00318 | | 9 | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1350

Page 4

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1356 | 286T1356 | | | AFT WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | |
| B-B | | | | 0-0 | 30-71-24 | B00100 | | = G | | | GD04374 | A.. | E | | 050-099 |
| B-B | | | | 0-0 | 30-71-23 | B00100 | | = G | | | GD04374 | A.. | E | | 150-199, 275-299 |
| C-A | | | | 0-0 | 30-71-23 | B00044 | | = P | | | SP00322 | | 9 | | ALL |
| C-B | | | | 0-0 | 30-71-23 | B00044 | | = G | | | GD00976 | A.. | E | | ALL |
| D-C | | | | 0-0 | 30-71-23 | B00233 | | = P | | | SP02708 | | 9 | | ALL |
| D-D | | | | 0-0 | 30-71-23 | B00233 | | = G | | | SP02750 | | 9 | | ALL |
| E-A | | | | 0-0 | 30-71-24 | B00093 | | = P | | | SP00358 | | 9 | | 050-099 |
| E-A | | | | 0-0 | 30-71-23 | B00093 | | = P | | | SP00358 | | 9 | | 150-199, 275-299 |
| E-C | | | | 0-0 | 30-71-24 | B00093 | | = G | | | GD04382 | A.. | E | | 050-099 |
| E-C | | | | 0-0 | 30-71-23 | B00093 | | = G | | | GD04382 | A.. | E | | 150-199, 275-299 |
| F-C | | | | 0-0 | 30-71-23 | B00237 | | = P | | | SP02718 | | 9 | | ALL |
| F-D | | | | 0-0 | 30-71-23 | B00237 | | = G | | | SP02726 | | 9 | | ALL |
| G-A | | | | 0-0 | 30-71-24 | B00359 | | BLK | | | GD05538 | A.. | 2 | | 050-099, 150-199 |
| G-B | | | | 0-0 | 30-71-24 | B00359 | | BKR | | | SP03384 | | 9 | | 050-099, 150-199 |
| H-A | | | | 0-0 | 30-71-23 | B00099 | | = P | | | SP00324 | | 9 | | 050-099 |
| H-A | | | | 0-0 | 30-71-24 | B00099 | | = P | | | SP03382 | | 9 | | 150-199 |
| H-B | | | | 0-0 | 30-71-23 | B00099 | | = G | | | GD00066 | A.. | 2 | | 050-099 |
| H-B | | | | 0-0 | 30-71-24 | B00099 | | = G | | | GD00066 | A.. | 2 | | 150-199 |
| K-A | | | | 0-0 | 38-15-11 | S00553 | | NC | | | SP01958 | | 9 | | ALL |
| K-B | | | | 0-0 | 38-15-11 | S00553 | | C | | | SP01960 | | 9 | | ALL |
| K-C | | | | 0-0 | SPARE | S00553 | | NO | | | S00553 | CAP | Y | | ALL |
| M-A | | | | 0-0 | 38-15-11 | S00333 | | NC | | | SP00596 | | 9 | | 050-099, 150-199 |
| M-B | | | | 0-0 | 38-15-11 | S00333 | | C | | | SP00594 | | 9 | | 050-099, 150-199 |
| M-C | | | | 0-0 | SPARE | S00333 | | NO | | | S00333 | CAP | Y | | 150-199 |
| N-A | | | | 0-0 | 30-71-24 | B00158 | | = P | | | SP00628 | | 9 | | 050-099 |
| N-A | | | | 0-0 | 30-71-23 | B00158 | | = P | | | SP00628 | | 9 | | 150-199, 277-299 |
| N-B | | | | 0-0 | 30-71-24 | B00158 | | = G | | | SP00354 | | 9 | | 050-099 |
| N-B | | | | 0-0 | 30-71-23 | B00158 | | = G | | | SP00354 | | 9 | | 150-199, 277-299 |
| N-C | | | | 0-0 | 30-71-24 | B00359 | | ORG | | | SP03385 | | 9 | | 050-099, 150-199 |
| N-D | | | | 0-0 | 30-71-24 | B00359 | | GRA | | | GD05538 | S.. | 2 | | 050-099, 150-199 |
| N-E | | | | 0-0 | 30-71-24 | B00356 | | BLK | | | SP03387 | | 9 | | 050-099, 150-199 |
| N-F | | | | 0-0 | 30-71-24 | B00359 | | BGR | | | SP03386 | | 9 | | 050-099, 150-199 |
| N-G | | | | 0-0 | 30-71-24 | B00356 | | GRA | | | SP03387 | | 9 | | 050-099, 150-199 |
| O-C | | | | 0-0 | 30-71-24 | B00357 | | BGR | | | SP03386 | | 9 | | 050-099, 150-154 |
| O-C | | | | 0-0 | 30-71-24 | B00357 | | BRN | | | SP03386 | | 9 | | 155-199 |
| O-D | | | | 0-0 | 30-71-24 | B00358 | | ORG | | | SP03385 | | 9 | | 050-099, 150-199 |
| O-E | | | | 0-0 | 30-71-24 | B00357 | | ORG | | | SP03385 | | 9 | | 050-099, 150-199 |
| O-F | | | | 0-0 | 30-71-24 | B00358 | | BLK | | | SP03387 | | 9 | | 050-099, 150-199 |
| P-D | | | | 0-0 | 30-71-24 | B00357 | | GRA | | | SP03387 | | 9 | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1350

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1356 | 286T1356 | | | AFT WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | |
| P-F | | | | 0-0 | 30-71-24 | B00357 | | BLK | | | SP03387 | | 9 | | 050-099, 150-199 |
| Q-C | | | | 0-0 | 30-71-24 | B00358 | | BGR | | | SP03386 | | 9 | | 050-099, 150-154 |
| Q-C | | | | 0-0 | 30-71-24 | B00358 | | BRN | | | SP03386 | | 9 | | 155-199 |
| Q-D | | | | 0-0 | 30-71-24 | B00356 | | ORG | | | SP03385 | | 9 | | 050-099, 150-199 |
| Q-E | | | | 0-0 | 30-71-24 | B00358 | | GRA | | | SP03387 | | 9 | | 050-099, 150-199 |
| Q-F | | | | 0-0 | 30-71-24 | B00356 | | BGR | | | SP03386 | | 9 | | 050-099, 150-154 |
| Q-F | | | | 0-0 | 30-71-24 | B00356 | | BRN | | | SP03386 | | 9 | | 155-199 |
| W1358 | 286T1358 | | | AFT WATER SUPPLY LINE & DRAIN LINE HEATERS | | | | | | | | | | | |
| 002 | 20 | PA | | 6-0 | 30-71-24 | D06308J | | | 2 | | SP00632 | | 9 | | 050-099 |
| 002 | 22 | PA | | 6-0 | 30-71-23 | D06308J | | | 2 | | SP00632 | | 9 | | 150-154, 275-299 |
| 002 | 20 | PA | | 6-0 | 30-71-23 | D06308J | | | 2 | | SP00632 | | 9 | | 155-199 |
| 003 | 20 | PA | | 30-0 | 30-71-23 | D06308J | | | 3 | | SP00342 | | 9 | | 050-099, 155-199 |
| 003 | 22 | PA | | 30-0 | 30-71-23 | D06308J | | | 3 | | SP00342 | | 9 | | 150-154, 275-299 |
| 004 | 20 | PA | | 7-0 | 30-71-23 | D06308J | | | 4 | | SP00446 | | 9 | | 050-099 |
| 004 | 20 | PA | | 7-0 | 30-71-24 | D06308J | | | 4 | | SP00446 | | 9 | | 150-199 |
| 005 | 22 | PA | | 24-0 | 30-71-23 | D06308J | | | 5 | | SP00630 | | 9 | | 275-276 |
| 006 | 20 | PA | | 24-0 | 30-71-23 | D06308J | | | 6 | | SP00332 | | 9 | | 050-099, 155-199 |
| 006 | 22 | PA | | 24-0 | 30-71-23 | D06308J | | | 6 | | SP00332 | | 9 | | 150-154, 275-299 |
| 008 | 20 | PA | | 30-0 | 30-71-23 | D06308J | | | 8 | | SP00338 | | 9 | | 050-099, 150-199, 275-276 |
| 008 | 22 | PA | | 6-0 | 30-71-23 | D06308J | | | 8 | | SP00338 | | 9 | | 277-299 |
| 015 | 16 | PA | | 31-0 | 30-71-24 | D06308J | | | 15 | | SP01840 | | 9 | | 050-099, 150-199 |
| 018 | 20 | PA | | 7-0 | 21-31-21 | D06308J | | | 18 | | D03148 | | 6 | | ALL |
| 02A | 20 | UA | | 5-0 | 21-31-21 | GD04714 | | S.. | E | | D03148 | | | FA | ALL |
| 02B | 20 | PA | | 5-0 | 21-31-21 | GD04714 | | S.. | E | | D03148 | | 2 | | ALL |
| 02C | 20 | PA | | 5-0 | 21-31-21 | GD04710 | | A.. | E | | D03148 | | 3 | | ALL |
| 02G | 20 | PA | | 5-0 | 21-31-21 | GD04710 | | A.. | E | | D03148 | | 7 | | ALL |
| 041 | 20 | PA | | 11-0 | 38-32-14 | D11966 | | | 1 | | GD05568 | | D.. | E | 050-099, 150-199, 277-299 |
| 042 | 20 | PA | | 5-0 | 38-32-14 | D11966 | | | 2 | | GD01498 | | S.. | E | 050-099, 150-199, 277-299 |
| 044 | 18 | PA | | 23-0 | 38-32-14 | D11966 | | | 4 | DK | D06306J | | 10 | DL | 050-099, 150-154 |
| 044 | 18 | PA | | 23-0 | 38-32-14 | SP05444 | | | 9 | | D06306J | | 10 | DL | 275-276 |
| 045 | 18 | PA | | 23-0 | 38-32-14 | D11966 | | | 5 | DK | D06306J | | 11 | DL | 050-099, 150-199, 277-299 |
| 045 | 18 | PA | | 23-0 | 38-32-14 | SP05442 | | | 9 | | D06306J | | 11 | DL | 275-276 |
| 101 | 24 | PK | | 24-0 | 21-26-11 | D06306J | | | 1 | | D00450 | | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1350

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1358 | 286T1358 | | | AFT WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | | | |
| 102 | 24 | | PK | 14-0 | 21-26-21 | D06306J | | 2 | | | | | D00608 | 5 | | | 050-099, 150-199, 275-278 |
| 102 | 24 | | PK | 12-0 | 21-26-21 | D06306J | | 2 | | | | | D00608 | 5 | | | 280-299 |
| 103 | 22 | | PA | 14-0 | 21-26-21 | D06306J | | 3 | | | | | D00608 | 2 | | | 050-099, 150-199, 275-278 |
| 103 | 22 | | PA | 12-0 | 21-26-21 | D06306J | | 3 | | | | | D00608 | 2 | | | 280-299 |
| 104 | 22 | | PA | 14-0 | 21-26-21 | D06306J | | 4 | | | | | D00608 | 3 | | | 050-099, 150-199, 275-278 |
| 104 | 22 | | PA | 12-0 | 21-26-21 | D06306J | | 4 | | | | | D00608 | 3 | | | 280-299 |
| 105 | 22 | | PA | 14-0 | 21-26-21 | D06306J | | 5 | | | | | D00608 | 4 | | | 050-099, 150-199, 275-278 |
| 105 | 22 | | PA | 12-0 | 21-26-21 | D06306J | | 5 | | | | | D00608 | 4 | | | 280-299 |
| 106 | 18 | | PA | 16-0 | 38-15-11 | D06306J | | 6 | DL | | | | D01294 | 3 | DK | | ALL |
| 107 | 18 | | PA | 16-0 | 38-15-11 | D06306J | | 7 | DL | | | | D01294 | 2 | DK | | ALL |
| 108 | 18 | | PA | 16-0 | 38-15-11 | D06306J | | 8 | DL | | | | D01294 | 1 | DK | | ALL |
| 109 | 22 | | PA | 23-0 | 38-32-11 | D06306J | | 9 | | | | | SM00004 | | 9 | | 050-099, 150-199, 275-278 |
| 109 | 22 | | PA | 41-0 | 38-32-11 | D06306J | | 9 | | | | | SM00004 | | 9 | | 280-299 |
| 10A | 16 | | PA | 6-0 | 21-26-11 | GD01340 | | S.. | E | | | | D00450 | 1 | | | ALL |
| 10C | 20 | | PA | 6-0 | 21-26-11 | GD01332 | | D.. | E | | | | D00450 | 3 | | | ALL |
| 114 | 16 | | PA | 24-0 | 21-26-11 | D06306J | | 14 | | | | | D00450 | 7 | | | ALL |
| 116 | 16 | | PA | 24-0 | 21-26-11 | D06306J | | 16 | | | | | D00450 | 4 | | | ALL |
| 118 | 16 | | PA | 24-0 | 21-26-11 | D06306J | | 18 | | | | | D00450 | 6 | | | ALL |
| 11F | 20 | | PA | 8-0 | 21-26-21 | GD04390 | | D.. | E | | | | D00608 | 6 | | | ALL |
| 11G | 20 | | PA | 8-0 | 21-26-21 | GD03566 | | S.. | E | | | | D00608 | 7 | | | ALL |
| 120 | 12 | | PA | 24-0 | 38-32-11 | D06306J | | 20 | | | | | D03818 | 2 | | | ALL |
| 122 | 12 | | PA | 24-0 | 38-32-11 | D06306J | | 22 | | | | | D03818 | 3 | | | ALL |
| 124 | 12 | | PA | 24-0 | 38-32-11 | D06306J | | 24 | | | | | D03818 | 4 | | | ALL |
| 12D | 18 | | PA | 5-0 | 38-15-11 | GD00066 | | A.. | 2 | | | | D01294 | 4 | DK | | ALL |
| 12E | 18 | | PA | 5-0 | 38-15-11 | GD00066 | | S.. | 2 | | | | D01294 | 5 | DK | | ALL |
| 13E | 18 | | PA | 0-6 | 38-32-11 | SM00004 | | | 9 | | | | D03818 | 5 | | | ALL |
| 13F | 18 | | PA | 10-0 | 38-32-11 | SP00602 | | | 9 | | | | D03818 | 6 | | | ALL |
| 13G | 12 | | PA | 4-0 | 38-32-11 | GD01498 | | S.. | E | | | | D03818 | 7 | | | ALL |
| 15X | 16 | | PA | 16-0 | 30-71-24 | SP02210 | | | 9 | | | | GD00066 | A.. | 2 | | 050-099, 150-199 |
| 220B | 24 | | PW | 7-0 | 21-31-21 | D06308J | | | 20 | | | | D03148 | 9 | | | ALL |
| 220R | 24 | | PW | 0-0 | 21-31-21 | D06308J | | | 21 | | | | D03148 | 10 | | | ALL |
| 220Z | | | | 0-0 | 21-31-21 | D06308J | | | 7 | | | | D03148 | | | FA | ALL |
| 222B | 20 | | PB | 7-0 | 21-31-21 | D06308J | | | 22 | | | | D03148 | 1 | | | ALL |
| 222R | 20 | | PB | 0-0 | 21-31-21 | D06308J | | | 24 | | | | D03148 | 5 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1350

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1358 | 286T1358 | | | AFT WATER SUPPLY LINE & DRAIN LINE HEATERS (continued) | | | | | | | | | | | |
| N-C | | | | | 0-0 | 30-71-24 | B00105 | | BLK | | GD00066 | A.. | 2 | | 050-099, 150-199 |
| N-D | | | | | 0-0 | 30-71-24 | B00105 | | ORG | | SP02214 | | 9 | | 050-099, 150-199 |
| N-E | | | | | 0-0 | 30-71-24 | B00105 | | BGR | | SP02216 | | 9 | | 050-099, 150-199 |
| N-F | | | | | 0-0 | 30-71-24 | B00105 | | GRA | | GD01894 | S.. | E | | 050-099, 150-199 |
| N-G | | | | | 0-0 | 30-71-24 | B00105 | | BKR | | SP01840 | | 9 | | 050-099, 150-199 |
| O-C | | | | | 0-0 | 30-71-24 | B00127 | | BLK | | SP02210 | | 9 | | 050-099, 150-199 |
| O-D | | | | | 0-0 | 30-71-24 | B00127 | | ORG | | SP02214 | | 9 | | 050-099, 150-199 |
| O-E | | | | | 0-0 | 30-71-24 | B00127 | | BGR | | SP02216 | | 9 | | 050-099, 150-199 |
| O-F | | | | | 0-0 | 30-71-24 | B00127 | | GRA | | SP02210 | | 9 | | 050-099, 150-199 |
| P-C | | | | | 0-0 | 30-71-24 | B00126 | | BLK | | SP02210 | | 9 | | 050-099, 150-199 |
| P-D | | | | | 0-0 | 30-71-24 | B00126 | | ORG | | SP02214 | | 9 | | 050-099, 150-199 |
| P-E | | | | | 0-0 | 30-71-24 | B00126 | | BGR | | SP02216 | | 9 | | 050-099, 150-199 |
| P-F | | | | | 0-0 | 30-71-24 | B00126 | | GRA | | SP02210 | | 9 | | 050-099, 150-199 |
| Q-C | | | | | 0-0 | 30-71-24 | B00089 | | BLK | | SP02210 | | 9 | | 050-099, 150-199 |
| Q-D | | | | | 0-0 | 30-71-24 | B00089 | | ORG | | SP02214 | | 9 | | 050-099, 150-199 |
| Q-E | | | | | 0-0 | 30-71-24 | B00089 | | BGR | | SP02216 | | 9 | | 050-099, 150-199 |
| Q-F | | | | | 0-0 | 30-71-24 | B00089 | | GRA | | SP02210 | | 9 | | 050-099, 150-199 |
| S-A | | | | | 0-0 | 30-71-23 | B00101 | | =P | | SP00630 | | 9 | | 275-276 |
| S-B | | | | | 0-0 | 30-71-23 | B00101 | | =G | | GD04586 | A.. | E | | 275-276 |
| T-A | | | | | 0-0 | 30-71-23 | B00102 | | =P | | SP00332 | | 9 | | ALL |
| T-B | | | | | 0-0 | 30-71-23 | B00102 | | =G | | GD00066 | A.. | 2 | | ALL |
| U-A | | | | | 0-0 | 30-71-23 | B00112 | | =P | | SP00338 | | 9 | | ALL |
| U-B | | | | | 0-0 | 30-71-23 | B00112 | | =G | | GD01490 | A.. | 2 | | 050-099, 150-199, 277-299 |
| U-B | | | | | 0-0 | 30-71-23 | B00112 | | =G | | GD04374 | A.. | E | | 275-276 |
| V-A | | | | | 0-0 | 30-71-24 | B00087 | | =P | | SP00632 | | 9 | | 050-099 |
| V-A | | | | | 0-0 | 30-71-23 | B00087 | | =P | | SP00632 | | 9 | | 150-199, 275-299 |
| V-B | | | | | 0-0 | 30-71-24 | B00087 | | =G | | GD01490 | A.. | 2 | | 050-099 |
| V-B | | | | | 0-0 | 30-71-23 | B00087 | | =G | | GD01490 | A.. | 2 | | 150-199, 275-299 |
| W-A | | | | | 0-0 | 30-71-23 | B00088 | | =P | | SP00342 | | 9 | | ALL |
| W-B | | | | | 0-0 | 30-71-23 | B00088 | | =G | | GD04374 | A.. | E | | ALL |
| Z-C | | | | | 0-0 | 30-71-23 | SP00446 | | | 9 | B00098 | =P | | | 050-099 |
| Z-C | | | | | 0-0 | 30-71-24 | SP00446 | | | 9 | B00098 | =P | | | 150-199 |
| Z-D | | | | | 0-0 | 30-71-23 | B00098 | | =G | | GD01490 | A.. | 2 | | 050-099 |
| Z-D | | | | | 0-0 | 30-71-24 | B00098 | | =G | | GD01490 | A.. | 2 | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W1350
Page 8 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1366 | 286T1366 | | | WATER FILL CONNECTION & SUPPLY LINE HEATERS | | | | | | | | | | | | | |
| 001 | 22 | | PA | 8-0 | 30-71-23 | D06302J | | 1 | | | | | SP00442 | | 9 | | 275-276 |
| 001 | 22 | | PA | 10-0 | 30-71-23 | D06302J | | 1 | | | | | SP00442 | | 9 | | 277-299 |
| 002 | 20 | | PA | 8-0 | 30-71-23 | D06302J | | 2 | | | | | SP01702 | | 9 | | 050-099, 155-199 |
| 002 | 22 | | PA | 8-0 | 30-71-23 | D06302J | | 2 | | | | | SP01702 | | 9 | | 150-154, 275-276 |
| 002 | 22 | | PA | 9-0 | 30-71-23 | D06302J | | 2 | | | | | SP01702 | | 9 | | 277-299 |
| 003 | 20 | | PA | 8-0 | 30-71-23 | D06302J | | 3 | | | | | SP01976 | | 9 | | 275-276 |
| 004 | 18 | | PA | 8-0 | 30-71-11 | D06302J | | 4 | DL | | | | SP02592 | | 9 | | 050-099, 150-163, 275-276 |
| 004 | 18 | | PA | 14-0 | 30-71-11 | D06302J | | 4 | DL | | | | SP02592 | | 9 | | 164-199, 277-299 |
| 005 | 20 | | PA | 8-0 | 30-71-23 | D06302J | | 5 | | | | | SP02746 | CAP | Y | | 050-099, 155-163 |
| 005 | 22 | | PA | 8-0 | 30-71-23 | D06302J | | 5 | | | | | SP02746 | CAP | Y | | 150-154, 275-276 |
| 005 | 20 | | PA | 14-0 | 30-71-23 | D06302J | | 5 | | | | | SP02746 | CAP | Y | | 164-199 |
| 005 | 22 | | PA | 14-0 | 30-71-23 | D06302J | | 5 | | | | | SP02746 | CAP | Y | | 277-299 |
| 03X | 20 | | PA | 6-0 | 30-71-23 | SP01978 | | | | 9 | | | GD03806 | A.. | E | | 275-276 |
| A-C | | | | 0-0 | 30-71-23 | B00480 | | | =P | | | | SP01702 | | 9 | | ALL |
| A-D | | | | 0-0 | 30-71-23 | B00480 | | | =G | | | | SP02746 | | 9 | | ALL |
| A-E | | | | 0-0 | 30-71-23 | B00241 | | | =P | | | | SP02746 | | 9 | | ALL |
| A-F | | | | 0-0 | 30-71-23 | B00241 | | | =G | | | | GD04608 | A.. | E | | ALL |
| B-C | | | | 0-0 | 30-71-11 | B00042 | | | =P | | | | SP02592 | | 9 | | ALL |
| B-D | | | | 0-0 | 30-71-11 | B00042 | | | =G | | | | GD04608 | A.. | E | | ALL |
| G-A | | | | 0-0 | 30-71-23 | B00110 | | | =P | | | | SP00442 | | 9 | | 275-299 |
| G-B | | | | 0-0 | 30-71-23 | B00110 | | | =G | | | | GD03806 | A.. | E | | 275-276 |
| G-B | | | | 0-0 | 30-71-23 | B00110 | | | =G | | | | GD04608 | A.. | E | | 277-299 |
| J-A | | | | 0-0 | 30-71-23 | B00149 | | | =P | | | | SP01702 | | 9 | | ALL |
| J-B | | | | 0-0 | 30-71-23 | B00149 | | | =G | | | | GD03806 | A.. | E | | ALL |
| N-A | | | | 0-0 | 30-71-23 | B00158 | | | =P | | | | SP01976 | | 9 | | 275-276 |
| N-B | | | | 0-0 | 30-71-23 | B00158 | | | =G | | | | SP01978 | | 9 | | 275-276 |
| W1369 | 286T1369 | | | DIGITAL AIDS RECORDER-E2-2 TO E5 | | | | | | | | | | | | | |
| 007 | 24 | | PK | 38-5 | SPARE | D04771J | | 7 | | | | | D04865J | | 7 | | 275-299 |
| 008 | 24 | | PK | 38-5 | SPARE | D04771J | | 8 | | | | | D04865J | | 8 | | 275-299 |
| 009 | 24 | | PK | 38-5 | SPARE | D04771J | | 9 | | | | | D04865J | | 9 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1360

Page 1 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1377 | 286T1377 | | | COAX CABLE-FWD AND AFT ZONE MULTIPLEXER | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-34-14 | D00547 | = C1 | | | D00535 | = C1 | | | ALL |
| 01CX | | | BX | A | 2-0 | 23-34-14 | D00547 | = A1 | | | D00535 | = A1 | | | ALL |
| W1379 | 286T1379 | | | RIGHT-FWD ZONE PSUD TO COLUMN TIMER DECODERS | | | | | | | | | | | |
| 002 | 16 | | | PA | 19-0 | 23-34-15 | D05197J | 2 | FL | | SM00001 | | 9 | | 050-099 |
| 002 | 16 | | | PA | 43-0 | 23-34-15 | D05197J | 2 | FL | | SM00001 | | 9 | | 150-157 |
| 002 | 16 | | | PA | 41-0 | 23-34-15 | D05197J | 2 | FL | | SM00001 | | S | | 162-199 |
| 002 | 16 | | | PA | 3-0 | 23-34-15 | D05197J | 2 | FL | | SM00001 | | 9 | | 275 |
| 002 | 16 | | | PA | 16-0 | 23-34-15 | D05197J | 2 | FL | | SM00001 | | 9 | | 276-299 |
| 003 | 16 | | | PA | 17-0 | 23-34-15 | D05197J | 3 | FL | | GD04728 | A.. | E | | 050-099, 162-199 |
| 003 | 16 | | | PA | 14-0 | 23-34-15 | D05197J | 3 | FL | | GD04728 | A.. | E | | 150-157, 276-299 |
| 003 | 16 | | | PA | 6-0 | 23-34-15 | D05197J | 3 | FL | | GD04728 | A.. | E | | 275 |
| 011 | 16 | | | PA | 27-0 | 23-34-15 | SM00001 | | | | SP00143 | | S | | 050-099 |
| 011 | 16 | | | PA | 72-0 | 23-34-15 | SM00001 | | | | SP00143 | | 9 | | 150-157 |
| 011 | 16 | | | PA | 72-0 | 23-34-15 | SM00001 | | S | | SP00143 | | 9 | | 162-199 |
| 011 | 16 | | | PA | 29-0 | 23-34-15 | SM00001 | | | | SP00143 | | 9 | | 275-299 |
| 012 | 16 | | | PA | 28-0 | 23-34-15 | SM00001 | | | | SM00002 | | 9 | | 275-299 |
| 013 | 16 | | | PA | 56-0 | 23-34-15 | D05429J | 2 | FL | | SM00001 | | 9 | | 050-099 |
| 013 | 16 | | | PA | 0-10 | 23-34-15 | SM00001 | | | | D05429J | 2 | FL | | 150-157 |
| 013 | 16 | | | PA | 0-10 | 23-34-15 | SM00001 | | S | | D05429J | 2 | FL | | 162-199 |
| 013 | 16 | | | PA | 0-10 | 23-34-15 | SM00002 | | | | D05429J | 2 | FL | | 275-278 |
| 014 | 16 | | | PA | 11-0 | 23-34-15 | D05429J | 3 | FL | | GD01460 | A.. | E | | 050-099 |
| 014 | 16 | | | PA | 6-0 | 23-34-15 | D05429J | 3 | FL | | GD04976 | A.. | E | | 150-199 |
| 014 | 16 | | | PA | 3-0 | 23-34-15 | D05429J | 3 | FL | | GD00717 | A.. | E | | 275-278 |
| 015 | 24 | | | PK | 0-10 | 23-34-15 | SM00003 | | | | D05429J | 1 | | | 275-278 |
| 016 | 24 | | | PK | 3-0 | 23-34-15 | D05429J | 4 | | | D05159J | 4 | | | 275-278 |
| 017 | 24 | | | PK | 0-10 | 23-34-15 | SM00003 | | | | D05159J | 1 | | | 275-299 |
| 018 | 16 | | | PA | 3-0 | 23-34-15 | D05159J | 3 | FL | | GD00717 | A.. | E | | 275-299 |
| 019 | 16 | | | PA | 0-10 | 23-34-15 | SM00002 | | | | D05159J | 2 | FL | | 275-299 |
| 020 | 24 | | | PK | 31-0 | 23-34-15 | D05275J | 4 | | | D05159J | 5 | | | 280-299 |
| 021 | 24 | | | PK | 31-0 | 23-34-15 | D05275J | 1 | | | SM00003 | | 9 | | 280-299 |
| 022 | 16 | | | PA | 11-0 | 23-34-15 | D05275J | 3 | FL | | GD04976 | A.. | E | | 280-299 |
| 023 | 16 | | | PA | 31-0 | 23-34-15 | D05275J | 2 | FL | | SM00002 | | 9 | | 280-299 |
| 024 | 24 | | | PK | 31-0 | 23-34-15 | D05275J | 5 | | | SM00004 | | W | | 280-299 |
| 026 | 16 | | | PA | 14-0 | 23-34-15 | D06105J | 2 | FM | | SM00001 | | 9 | | 050-099 |
| 026 | 16 | | | PA | 51-0 | 23-34-15 | D06105J | 2 | FL | | SM00001 | | S | | 162-199 |
| 027 | 16 | | | PA | 3-0 | 23-34-15 | D06105J | 3 | FM | | GD06735 | A.. | 2 | | 050-099 |
| 027 | 16 | | | PA | 6-0 | 23-34-15 | D06105J | 3 | FL | | GD06735 | A.. | 2 | | 162-199 |
| 301B | 24 | | | PM | 19-0 | 23-34-15 | D05197J | 4 | | | SM00006 | | S | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W1370

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1379 | 286T1379 | | | RIGHT-FWD ZONE PSUD TO COLUMN TIMER DECODERS (continued) | | | | | | | | | | | | | |
| 301B | 24 | | PM | MA | 33-0 | 23-34-15 | D05197J | | 4 | | | | D00497 | 2 | | | 150-157, 276-299 |
| 301B | 24 | | PM | MA | 21-0 | 23-34-15 | D05197J | | 4 | | | | D00497 | 2 | | | 275 |
| 301R | 24 | | PM | MA | 0-0 | 23-34-15 | D05197J | | 5 | | | | SM00008 | | S | | 050-099, 162-199 |
| 301R | 24 | | PM | MA | 0-0 | 23-34-15 | D05197J | | 5 | | | | D00497 | 1 | | | 150-157, 275-299 |
| 301Y | 24 | | PM | MA | 0-0 | 23-34-15 | D05197J | | 1 | | | | SM00005 | | S | | 050-099, 162-199 |
| 301Y | 24 | | PM | MA | 0-0 | 23-34-15 | D05197J | | 1 | | | | D00497 | 3 | | | 150-157, 275-299 |
| 303B | 24 | | PM | MC | 74-0 | 23-34-15 | D05429J | | 4 | | | | D00511 | 2 | | | 050-099 |
| 303B | 24 | | PM | MC | 65-0 | 23-34-15 | D00511 | | 2 | | | | D05429J | 4 | | | 150-199 |
| 303B | 24 | | PM | MC | 46-0 | 23-34-15 | D00511 | | 2 | | | | D05159J | 5 | | | 275-278 |
| 303B | 24 | | PM | MC | 46-0 | 23-34-15 | D00511 | | 2 | | | | D05159J | 4 | | | 280-299 |
| 303R | 24 | | PM | MC | 0-0 | 23-34-15 | D05429J | | 5 | | | | D00511 | 1 | | | 050-099 |
| 303R | 24 | | PM | MC | 0-0 | 23-34-15 | D00511 | | 1 | | | | D05429J | 5 | | | 150-199, 275-278 |
| 303R | 24 | | PM | MC | 0-0 | 23-34-15 | D00511 | | 1 | | | | SM00004 | | W | | 280-299 |
| 303Y | 24 | | PM | MC | 0-0 | 23-34-15 | D05429J | | 1 | | | | D00511 | 3 | | | 050-099 |
| 303Y | 24 | | PM | MC | 0-0 | 23-34-15 | D00511 | | 3 | | | | D05429J | 1 | | | 150-199 |
| 303Y | 24 | | PM | MC | 0-0 | 23-34-15 | D00511 | | 3 | | | | SM00003 | | 9 | | 275-299 |
| 304B | 24 | | PM | MD | 14-0 | 23-34-15 | D06105J | | 4 | | | | SM00007 | | S | | 050-099 |
| 304B | 24 | | PM | MD | 16-0 | 23-34-15 | D06105J | | 4 | | | | SM00007 | | S | | 162-199 |
| 304R | 24 | | PM | MD | 0-0 | 23-34-15 | D06105J | | 5 | | | | SM00006 | | S | | 050-099, 162-199 |
| 304Y | 24 | | PM | MD | 0-0 | 23-34-15 | D06105J | | 1 | | | | SM00005 | | S | | 050-099, 162-199 |
| 305B | 24 | | PM | ME | 19-0 | 23-34-15 | D00497 | | 2 | | | | SM00007 | | S | | 050-099, 162-199 |
| 305R | 24 | | PM | ME | 0-0 | 23-34-15 | D00497 | | 1 | | | | SM00008 | | S | | 050-099, 162-199 |
| 305Y | 24 | | PM | ME | 0-0 | 23-34-15 | D00497 | | 3 | | | | SM00005 | | S | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W1370

Page 2 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1381 | 286T1381 | | | CENTER-FWD ZONE PSUD TO COLUMN TIMER DECODERS | | | | | | | | | | | |
| 002 | 16 | | PA | | 1-0 | 23-34-17 | D05199J | 2 | FL | | SM00001 | | 9 | | ALL |
| 003 | 16 | | PA | | 8-0 | 23-34-17 | D05199J | 3 | FL | | GD01022 | A.. | E | | 050-099 |
| 003 | 16 | | PA | | 5-0 | 23-34-17 | D05199J | 3 | FL | | GD00119 | A.. | 2 | | 150-157, 280-299 |
| 003 | 16 | | PA | | 19-0 | 23-34-17 | D05199J | 3 | FL | | GD00119 | A.. | 2 | | 162-199 |
| 003 | 16 | | PA | | 4-3 | 23-34-17 | D05199J | 3 | FL | | GD00119 | A.. | 2 | | 275-278 |
| 007 | 16 | | PA | | 1-0 | 23-34-17 | D05161J | 2 | FL | | SM00002 | | 9 | | 050-099, 150-199, 275-278 |
| 011 | 12 | | PA | | 42-0 | 23-34-17 | SM00001 | | 9 | | SP00141 | | S | | 050-099 |
| 011 | 12 | | PA | | 29-0 | 23-34-17 | SM00001 | | 9 | | SP00141 | | 9 | | 150-157 |
| 011 | 12 | | PA | | 43-0 | 23-34-17 | SM00001 | | 9 | | SP00141 | | 9 | | 162-199 |
| 011 | 12 | | PA | | 27-7 | 23-34-17 | SM00001 | | 9 | | SP00141 | | 9 | | 275-278 |
| 011 | 12 | | PA | | 28-0 | 23-34-17 | SM00001 | | 9 | | SP00141 | | 9 | | 280-299 |
| 012 | 12 | | PA | | 48-0 | 23-34-17 | SM00001 | | 9 | | SM00002 | | 9 | | 050-099 |
| 012 | 12 | | PA | | 30-0 | 23-34-17 | SM00001 | | 9 | | SM00002 | | 9 | | 150-157, 275-278 |
| 012 | 12 | | PA | | 25-0 | 23-34-17 | SM00001 | | 9 | | SM00002 | | 9 | | 162-199 |
| 013 | 24 | | PK | | 1-0 | 23-34-17 | D05161J | 1 | | | SM00003 | | 9 | | 275-278 |
| 014 | 24 | | PK | | 1-9 | 23-34-17 | D05161J | 4 | | | D05527J | 4 | | | 275-278 |
| 015 | 24 | | PK | | 1-0 | 23-34-17 | D05527J | 1 | | | SM00003 | | 9 | | 275-299 |
| 016 | 16 | | PA | | 4-8 | 23-34-17 | D05527J | 3 | FL | | GD01930 | A.. | 2 | | 275-278 |
| 016 | 16 | | PA | | 6-0 | 23-34-17 | D05527J | 3 | FL | | GD01930 | A.. | 2 | | 280-299 |
| 017 | 16 | | PA | | 1-0 | 23-34-17 | D05527J | 2 | FL | | SM00002 | | 9 | | 275-299 |
| 018 | 16 | | PA | | 7-0 | 23-34-17 | D05161J | 3 | FL | | GD01944 | A.. | 2 | | 050-099 |
| 018 | 16 | | PA | | 6-0 | 23-34-17 | D05161J | 3 | FL | | GD01930 | A.. | 2 | | 150-199 |
| 018 | 16 | | PA | | 4-8 | 23-34-17 | D05161J | 3 | FL | | GD01930 | A.. | 2 | | 275-278 |
| 019 | 12 | | PA | | 57-0 | 23-34-17 | SP00561 | | 9 | | SM00002 | | 9 | | 280-299 |
| 020 | 24 | | PK | | 23-0 | 23-34-17 | D05253J | 4 | | | D05527J | 5 | | | 280-299 |
| 021 | 24 | | PK | | 23-0 | 23-34-17 | D05253J | 1 | | | SM00003 | | 9 | | 280-299 |
| 022 | 16 | | PA | | 15-0 | 23-34-17 | D05253J | 3 | FL | | GD04868 | A.. | E | | 280-299 |
| 023 | 16 | | PA | | 23-0 | 23-34-17 | D05253J | 2 | FL | | SM00002 | | 9 | | 280-299 |
| 024 | 24 | | PK | | 23-0 | 23-34-17 | D05253J | 5 | | | SM00004 | | W | | 280-299 |
| 301B | 24 | | PM | MA | 44-0 | 23-34-17 | D05199J | 4 | | | D00501 | 2 | | | 050-099 |
| 301B | 24 | | PM | MA | 31-0 | 23-34-17 | D05199J | 4 | | | D00501 | 2 | | | 150-157 |
| 301B | 24 | | PM | MA | 45-0 | 23-34-17 | D05199J | 4 | | | D00501 | 2 | | | 162-199 |
| 301B | 24 | | PM | MA | 30-2 | 23-34-17 | D05199J | 4 | | | D00501 | 2 | | | 275-278 |
| 301B | 24 | | PM | MA | 32-0 | 23-34-17 | D05199J | 4 | | | D00501 | 2 | | | 280-299 |
| 301R | 24 | | PM | MA | 0-0 | 23-34-17 | D05199J | 5 | | | D00501 | 1 | | | ALL |
| 301Y | 24 | | PM | MA | 0-0 | 23-34-17 | D05199J | 1 | | | D00501 | 3 | | | ALL |
| 303B | 24 | | PM | MC | 83-0 | 23-34-17 | D05161J | 4 | | | D00515 | 2 | | | 050-099 |
| 303B | 24 | | PM | MC | 60-0 | 23-34-17 | D00515 | 2 | | | D05161J | 4 | | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1380

Page 1

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-----|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1381 | 286T1381 | | | CENTER-FWD ZONE PSUD TO COLUMN TIMER DECODERS (continued) | | | | | | | | | | | | | |
| 303B | 24 | | PM | MC | 60-7 | 23-34-17 | D00515 | | 2 | | | | D05527J | | 5 | | 275-278 |
| 303B | 24 | | PM | MC | 70-0 | 23-34-17 | D00515 | | 2 | | | | D05527J | | 4 | | 280-299 |
| 303R | 24 | | PM | MC | 0-0 | 23-34-17 | D05161J | | 5 | | | | D00515 | | 1 | | 050-099 |
| 303R | 24 | | PM | MC | 0-0 | 23-34-17 | D00515 | | 1 | | | | D05161J | | 5 | | 150-199, 275-278 |
| 303R | 24 | | PM | MC | 0-0 | 23-34-17 | D00515 | | 1 | | | | SM00004 | | | W | 280-299 |
| 303Y | 24 | | PM | MC | 0-0 | 23-34-17 | D05161J | | 1 | | | | D00515 | | 3 | | 050-099 |
| 303Y | 24 | | PM | MC | 0-0 | 23-34-17 | D00515 | | 3 | | | | D05161J | | 1 | | 150-199 |
| 303Y | 24 | | PM | MC | 0-0 | 23-34-17 | D00515 | | 3 | | | | SM00003 | | | 9 | 275-299 |
| W1383 | 286T1383 | | | LEFT-FWD ZONE PSUD TO COLUMN TIMER DECODERS | | | | | | | | | | | | | |
| 002 | 16 | | PA | | 33-0 | 23-34-16 | D05155J | | 2 | FL | | | SM00001 | | | 9 | 050-099 |
| 002 | 16 | | PA | | 43-0 | 23-34-16 | D05155J | | 2 | FL | | | SM00001 | | | 9 | 150-199 |
| 002 | 16 | | PA | | 13-0 | 23-34-16 | D05155J | | 2 | FL | | | SM00001 | | | 9 | 275 |
| 002 | 16 | | PA | | 23-10 | 23-34-16 | D05155J | | 2 | FL | | | SM00001 | | | 9 | 276-278 |
| 002 | 16 | | PA | | 24-0 | 23-34-16 | D05155J | | 2 | FL | | | SM00001 | | | 9 | 280-299 |
| 003 | 16 | | PA | | 12-0 | 23-34-16 | D05155J | | 3 | FL | | | GD00123 | | A.. | E | 050-099 |
| 003 | 16 | | PA | | 14-0 | 23-34-16 | D05155J | | 3 | FL | | | GD04732 | | A.. | E | 150-199, 280-299 |
| 003 | 16 | | PA | | 7-0 | 23-34-16 | D05155J | | 3 | FL | | | GD04732 | | A.. | E | 275 |
| 003 | 16 | | PA | | 13-3 | 23-34-16 | D05155J | | 3 | FL | | | GD04732 | | A.. | E | 276-278 |
| 011 | 16 | | PA | | 17-0 | 23-34-16 | SM00001 | | | | | | SP00139 | | | S | 050-099 |
| 011 | 16 | | PA | | 70-0 | 23-34-16 | SM00001 | | | | | | SP00139 | | | 9 | 150-199 |
| 011 | 16 | | PA | | 16-0 | 23-34-16 | SM00001 | | | | | | SP00139 | | | 9 | 275, 280-299 |
| 011 | 16 | | PA | | 15-0 | 23-34-16 | SM00001 | | | | | | SP00139 | | | 9 | 276-278 |
| 012 | 16 | | PA | | 37-0 | 23-34-16 | SM00001 | | | | | | SM00002 | | | 9 | 275 |
| 012 | 16 | | PA | | 35-4 | 23-34-16 | SM00001 | | | | | | SM00002 | | | 9 | 276-278 |
| 012 | 16 | | PA | | 36-0 | 23-34-16 | SM00001 | | | | | | SM00002 | | | 9 | 280-299 |
| 013 | 24 | | PK | | 0-10 | 23-34-16 | D05157J | | 1 | | | | SM00003 | | | 9 | 275-278 |
| 014 | 24 | | PK | | 3-0 | 23-34-16 | D05157J | | 4 | | | | D05501J | | 4 | | 275 |
| 014 | 24 | | PK | | 1-8 | 23-34-16 | D05157J | | 4 | | | | D05501J | | 4 | | 276-278 |
| 015 | 24 | | PK | | 0-10 | 23-34-16 | D05501J | | 1 | | | | SM00003 | | | 9 | 275-299 |
| 016 | 16 | | PA | | 5-0 | 23-34-16 | D05501J | | 3 | FL | | | GD00719 | | A.. | E | 275, 280-299 |
| 016 | 16 | | PA | | 3-8 | 23-34-16 | D05501J | | 3 | FL | | | GD00719 | | A.. | E | 276-278 |
| 017 | 16 | | PA | | 0-10 | 23-34-16 | D05501J | | 2 | FL | | | SM00002 | | | 9 | 275-299 |
| 018 | 16 | | PA | | 10-0 | 23-34-16 | D05157J | | 3 | FL | | | GD01550 | | A.. | E | 050-099 |
| 018 | 16 | | PA | | 10-0 | 23-34-16 | D05157J | | 3 | FL | | | GD04864 | | A.. | E | 150-199 |
| 018 | 16 | | PA | | 5-0 | 23-34-16 | D05157J | | 3 | FL | | | GD00719 | | A.. | E | 275 |
| 018 | 16 | | PA | | 3-9 | 23-34-16 | D05157J | | 3 | FL | | | GD00719 | | A.. | E | 276-278 |
| 019 | 16 | | PA | | 64-0 | 23-34-16 | D05157J | | 2 | FL | | | SM00001 | | | 9 | 050-099 |
| 019 | 16 | | PA | | 0-10 | 23-34-16 | D05157J | | 2 | FL | | | SM00001 | | | 9 | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1380

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|-------|------|------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1383 | 286T1383 | LEFT-FWD ZONE PSUD TO COLUMN TIMER DECODERS (continued) | | | | | | | | | | | | | |
| 019 | 16 | PA | | | 0-10 | 23-34-16 | D05157J | 2 | FL | | SM00002 | | 9 | | 275-278 |
| 020 | 24 | PK | | | 31-0 | 23-34-16 | D05251J | 4 | | | D05501J | | 5 | | 280-299 |
| 021 | 24 | PK | | | 30-0 | 23-34-16 | D05251J | 1 | | | SM00003 | | 9 | | 280-299 |
| 022 | 16 | PA | | | 6-0 | 23-34-16 | D05251J | 3 | FL | | GD04864 | A.. | E | | 280-299 |
| 023 | 16 | PA | | | 30-0 | 23-34-16 | D05251J | 2 | FL | | SM00002 | | 9 | | 280-299 |
| 024 | 24 | PK | | | 30-0 | 23-34-16 | D05251J | 5 | | | SM00004 | | W | | 280-299 |
| 301B | 24 | PM | MA | | 52-0 | 23-34-16 | D05155J | 4 | | | D00505 | | 2 | | 050-099 |
| 301B | 24 | PM | MA | | 53-0 | 23-34-16 | D05155J | 4 | | | D00505 | | 2 | | 150-199 |
| 301B | 24 | PM | MA | | 33-0 | 23-34-16 | D05155J | 4 | | | D00505 | | 2 | | 275 |
| 301B | 24 | PM | MA | | 44-1 | 23-34-16 | D05155J | 4 | | | D00505 | | 2 | | 276-278 |
| 301B | 24 | PM | MA | | 44-0 | 23-34-16 | D05155J | 4 | | | D00505 | | 2 | | 280-299 |
| 301R | 24 | PM | MA | | 0-0 | 23-34-16 | D05155J | 5 | | | D00505 | | 1 | | ALL |
| 301Y | 24 | PM | MA | | 0-0 | 23-34-16 | D05155J | 1 | | | D00505 | | 3 | | ALL |
| 303B | 24 | PM | MC | | 85-0 | 23-34-16 | D05157J | 4 | | | D00519 | | 2 | | 050-099 |
| 303B | 24 | PM | MC | | 77-0 | 23-34-16 | D00519 | 2 | | | D05157J | | 4 | | 150-199 |
| 303B | 24 | PM | MC | | 57-0 | 23-34-16 | D00519 | 2 | | | D05501J | | 5 | | 275 |
| 303B | 24 | PM | MC | | 57-5 | 23-34-16 | D00519 | 2 | | | D05501J | | 5 | | 276-278 |
| 303B | 24 | PM | MC | | 57-0 | 23-34-16 | D00519 | 2 | | | D05501J | | 4 | | 280-299 |
| 303R | 24 | PM | MC | | 0-0 | 23-34-16 | D05157J | 5 | | | D00519 | | 1 | | 050-099 |
| 303R | 24 | PM | MC | | 0-0 | 23-34-16 | D00519 | 1 | | | D05157J | | 5 | | 150-199, 275-278 |
| 303R | 24 | PM | MC | | 0-0 | 23-34-16 | D00519 | 1 | | | SM00004 | | W | | 280-299 |
| 303Y | 24 | PM | MC | | 0-0 | 23-34-16 | D05157J | 1 | | | D00519 | | 3 | | 050-099 |
| 303Y | 24 | PM | MC | | 0-0 | 23-34-16 | D00519 | 3 | | | D05157J | | 1 | | 150-199 |
| 303Y | 24 | PM | MC | | 0-0 | 23-34-16 | D00519 | 3 | | | SM00003 | | 9 | | 275-299 |
| W1387 | 286T1387 | CENTER-AFT ZONE PSUD POWER INPUT | | | | | | | | | | | | | |
| 002 | 16 | PA | | | 1-0 | 23-34-19 | D05185J | 2 | FL | | SM00001 | | 9 | | ALL |
| 003 | 16 | PA | | | 5-0 | 23-34-19 | D05185J | 3 | FL | | GD01758 | A.. | 2 | | 050-099 |
| 003 | 16 | PA | | | 6-0 | 23-34-19 | D05185J | 3 | FL | | GD01758 | A.. | 2 | | 150-199, 275-299 |
| 007 | 16 | PA | | | 6-0 | 23-34-19 | D05181J | 3 | FL | | GD00723 | A.. | 2 | | ALL |
| 008 | 24 | PK | | | 1-0 | 23-34-19 | D05181J | 4 | | | D05181J | | 5 | | ALL |
| 009 | 16 | PA | | | 1-0 | 23-34-19 | D05181J | 2 | FL | | SM00002 | | 9 | | ALL |
| 010 | 12 | PA | | | 35-0 | 23-34-19 | SM00001 | | | | SM00002 | | 9 | | 050-099 |
| 010 | 12 | PA | | | 45-0 | 23-34-19 | SM00001 | | | | SM00002 | | 9 | | 150-199, 275-299 |
| 011 | 12 | PA | | | 104-0 | 23-34-19 | SM00001 | | | | SP00055 | | S | | 050-099 |
| 011 | 12 | PA | | | 122-0 | 23-34-19 | SM00001 | | | | SP00055 | | 9 | | 150-199, 275-299 |
| 012 | 24 | PK | | | 2-0 | 23-34-19 | D05185J | 1 | | | SM00003 | | 9 | | 050-099 |
| 012 | 24 | PK | | | 1-0 | 23-34-19 | D05185J | 1 | | | SM00003 | | 9 | | 150-199, 275-278 |
| 013 | 24 | PK | | | 1-0 | 23-34-19 | D05185J | 4 | | | D05491J | | 4 | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W1380
Page 3
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1387 | 286T1387 | | | CENTER-AFT ZONE PSUD POWER INPUT (continued) | | | | | | | | | | | | | | |
| 013 | 24 | | PK | 2-0 | 23-34-19 | D05491J | | 4 | | | | | D05185J | | 4 | | | 150-199, 275-278 |
| 014 | 24 | | PK | 2-0 | 23-34-19 | SM00003 | | | 9 | | | | D05491J | | 1 | | | 050-099 |
| 014 | 24 | | PK | 1-0 | 23-34-19 | D05491J | | 1 | | | | | SM00003 | | | 9 | | 150-199, 275-278 |
| 015 | 16 | | PA | 5-0 | 23-34-19 | D05491J | | 3 | FL | | | | GD01758 | A.. | 2 | | | 050-099 |
| 015 | 16 | | PA | 6-0 | 23-34-19 | D05491J | | 3 | FL | | | | GD01758 | A.. | 2 | | | 150-199, 275-278 |
| 016 | 16 | | PA | 2-0 | 23-34-19 | D05491J | | 2 | FL | | | | SM00001 | | 9 | | | 050-099 |
| 016 | 16 | | PA | 1-0 | 23-34-19 | D05491J | | 2 | FL | | | | SM00001 | | 9 | | | 150-199, 275-278 |
| 302B | 24 | | PM MB | 81-0 | 23-34-19 | D01867 | | 2 | | | | | D05491J | | 5 | | | 050-099 |
| 302B | 24 | | PM MB | 87-0 | 23-34-19 | D01867 | | 2 | | | | | D05491J | | 5 | | | 150-199, 275-278 |
| 302B | 24 | | PM MB | 112-0 | 23-34-19 | D01867 | | 2 | | | | | D05185J | | 4 | | | 280-299 |
| 302R | 24 | | PM MB | 0-0 | 23-34-19 | D01867 | | 1 | | | | | D05185J | | 5 | | | ALL |
| 302Y | 24 | | PM MB | 0-0 | 23-34-19 | D01867 | | 3 | | | | | SM00003 | | | 9 | | 050-099, 150-199, 275-278 |
| 302Y | 24 | | PM MB | 0-0 | 23-34-19 | D01867 | | 3 | | | | | D05185J | | 1 | | | 280-299 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1398 | 286T1398 | | | LEFT ESCAPE HATCH HEATER BLANKET STATION 871 | | | | | | | | | | | |
| 001 | 20 | | PA | | 3-0 | 21-45-22 | D06810P | | 1 | | SP05062 | | | 9 | ALL |
| 002 | 20 | | PA | | 3-0 | 21-45-22 | D06810P | | 2 | | SP05064 | | | 9 | ALL |
| 003 | 18 | | PA | | 4-0 | 21-45-22 | D06810P | | 3 | DL | GD05794 | S.. | E | | ALL |
| A-A | | | | | 0-0 | 21-45-22 | SP05062 | | | | B00406 | WB | | | ALL |
| A-B | | | | | 0-0 | 21-45-22 | SP05064 | | | | B00406 | W | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1390
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1400 | 286T1400 | | | RIGHT ESCAPE HATCH HEATER BLANKET STATION 871 | | | | | | | | | | | | | |
| 001 | 20 | | PA | 3-0 | 21-45-22 | D06814P | | 1 | | | | | SP05066 | | 9 | | ALL |
| 002 | 20 | | PA | 3-0 | 21-45-22 | D06814P | | 2 | | | | | SP05068 | | 9 | | ALL |
| 003 | 18 | | PA | 4-0 | 21-45-22 | D06814P | | 3 | DL | | | | GD05798 | S.. | E | | ALL |
| A-A | | | | 0-0 | 21-45-22 | SP05066 | | | | 9 | | | B00408 | WB | | | ALL |
| A-B | | | | 0-0 | 21-45-22 | SP05068 | | | | 9 | | | B00408 | W | | | ALL |
| W1407 | 286T1407 | | | VIDEO SYSTEM-FROM E2-5 TO VIDEO CONTROL CENTER | | | | | | | | | | | | | |
| 001 | 24 | | PK | 38-0 | 23-32-12 | D05593J | | 1 | | | | | D06035J | | 4 | | 050-099, 150-199 |
| 001 | 24 | | PK | 55-9 | 23-32-12 | D05593J | | 1 | | | | | D06666J | | 42 | | 275 |
| 001 | 24 | | PK | 55-11 | 23-32-12 | D05593J | | 1 | | | | | D06666J | | 42 | | 276-299 |
| 002 | 24 | | PK | 38-0 | 23-32-12 | D05593J | | 2 | | | | | D06035J | | 5 | | 050-099, 150-199 |
| 002 | 24 | | PK | 55-9 | 23-32-12 | D05593J | | 2 | | | | | D06666J | | 28 | | 275 |
| 002 | 24 | | PK | 55-11 | 23-32-12 | D05593J | | 2 | | | | | D06666J | | 28 | | 276-299 |
| 003 | 24 | | PV A | 38-0 | 23-32-12 | D05593J | | 3 | | | | | D06035J | | 6 | | 050-099 |
| 003 | 24 | | PV AC | 38-0 | 23-32-12 | D05593J | | 3 | | | | | D06035J | | 6 | | 150-199 |
| 003Z | | | A | 0-0 | 23-32-12 | D05593J | | 4 | | | | | D06035J | | 7 | | 050-099 |
| 003Z | | | AC | 0-0 | 23-32-12 | D05593J | | 4 | | | | | D06035J | | 7 | | 150-199 |
| 005 | 24 | | PK | 38-0 | 23-32-12 | D05593J | | 5 | | | | | D06035J | | 8 | | 050-099, 150-199 |
| 005 | 24 | | PK | 55-9 | 23-32-12 | D05593J | | 5 | | | | | D06666J | | 9 | | 275 |
| 005 | 24 | | PK | 55-11 | 23-32-12 | D05593J | | 5 | | | | | D06666J | | 9 | | 276-299 |
| 006 | 24 | | PV B | 38-0 | 23-32-12 | D05593J | | 6 | | | | | D06035J | | 9 | | 050-099 |
| 006 | 24 | | PV AF | 38-0 | 23-32-12 | D05593J | | 6 | | | | | D06035J | | 9 | | 150-199 |
| 006Z | | | B | 0-0 | 23-32-12 | D05593J | | 7 | | | | | D06035J | | | | 050-099 |
| 006Z | | | AF | 0-0 | 23-32-12 | D05593J | | 7 | | | | | D06035J | | | | 150-199 |
| 008 | 24 | | PV C | 38-0 | 23-32-12 | D05593J | | 8 | | | | | D06035J | | 10 | | 050-099 |
| 008 | 24 | | PV AH | 38-0 | 23-32-12 | D05593J | | 8 | | | | | D06035J | | 10 | | 150-199 |
| 008Z | | | C | 0-0 | 23-32-12 | D05593J | | 9 | | | | | D06035J | | | | 050-099 |
| 008Z | | | AH | 0-0 | 23-32-12 | D05593J | | 9 | | | | | D06035J | | | | 150-199 |
| 010 | 24 | | PV D | 38-0 | 23-32-12 | D05593J | | 10 | | | | | D06035J | | 11 | | 050-099 |
| 010 | 24 | | PV AJ | 38-0 | 23-32-12 | D05593J | | 10 | | | | | D06035J | | 11 | | 150-199 |
| 010Z | | | D | 0-0 | 23-32-12 | D05593J | | 11 | | | | | D06035J | | | | 050-099 |
| 010Z | | | AJ | 0-0 | 23-32-12 | D05593J | | 11 | | | | | D06035J | | | | 150-199 |
| 012 | 24 | | PV E | 38-0 | 23-32-12 | D05593J | | 12 | | | | | D06035J | | 12 | | 050-099 |
| 012 | 24 | | PV AL | 38-0 | 23-32-12 | D05593J | | 12 | | | | | D06035J | | 12 | | 150-199 |
| 012Z | | | E | 0-0 | 23-32-12 | D05593J | | 13 | | | | | D06035J | | | | 050-099 |
| 012Z | | | AL | 0-0 | 23-32-12 | D05593J | | 13 | | | | | D06035J | | | | 150-199 |
| 014 | 20 | | PA | 18-1 | 23-32-11 | D05593J | | 14 | | | | | SP00429 | | S | | 050-099, 150-199 |
| 014 | 20 | | PA | 19-0 | 23-32-11 | D05593J | | 14 | | | | | SP00429 | | S | | 275 |
| 014 | 20 | | PA | 18-4 | 23-32-11 | D05593J | | 14 | | | | | SP00429 | | S | | 276-299 |

WIRE LIST

D280T132

91-21-11

Section W1400

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1407 | 286T1407 | | | VIDEO SYSTEM-FROM E2-5 TO VIDEO CONTROL CENTER (continued) | | | | | | | | | | | |
| 015 | 20 | | PA | | 28-4 | 23-32-11 | SP00429 | | S | | D06035J | 21 | | | 050-099 |
| 015 | 20 | | PA | | 28-4 | 23-32-11 | D06035J | 21 | | | SP00429 | | S | | 150-199 |
| 015 | 20 | | PA | | 46-0 | 23-32-11 | D06666J | 4 | | | SP00429 | | S | | 275 |
| 015 | 20 | | PA | | 45-6 | 23-32-11 | D06666J | 4 | | | SP00429 | | S | | 276-299 |
| 017 | 20 | | PA | | 3-10 | 23-32-11 | D06035J | 3 | | | GD06733 | S.. | 2 | | 050-099, 150-199 |
| 019 | 16 | | PA | | 3-10 | 23-32-11 | D06035J | 23 | | | GD06733 | D.. | 2 | | 050-099, 150-199 |
| 019 | 20 | | PA | | 6-6 | 23-32-11 | D06666J | 5 | | | GD00434 | D.. | 2 | | 275 |
| 019 | 20 | | PA | | 6-7 | 23-32-11 | D06666J | 5 | | | GD00434 | D.. | 2 | | 276-299 |
| 030 | 24 | | PV | BE | 38-0 | 23-32-12 | D05593J | 20 | | | D06035J | 13 | | | 050-099, 150-199 |
| 030Z | | | | BE | 0-0 | 23-32-12 | D05593J | 21 | | | D06035J | | | FA | 050-099, 150-199 |
| 031 | 24 | | PV | BF | 38-0 | 23-32-12 | D05593J | 22 | | | D06035J | 14 | | | 050-099, 150-199 |
| 031Z | | | | BF | 0-0 | 23-32-12 | D05593J | 23 | | | D06035J | | | FA | 050-099, 150-199 |
| 035 | 22 | | PA | | 38-0 | 23-32-12 | D05593J | 18 | | | D06035J | 18 | | | 050-099, 150-199 |
| 036 | 22 | | PA | | 38-0 | 23-32-12 | D05593J | 16 | | | D06035J | 16 | | | 050-099, 150-199 |
| 037 | 22 | | PA | | 38-0 | 23-32-12 | D05593J | 17 | | | D06035J | 17 | | | 050-099, 150-199 |
| 201B | 24 | | PW | IA | 55-9 | 23-32-12 | D05593J | 4 | | | D06666J | 3 | | | 275 |
| 201B | 24 | | PW | IA | 55-11 | 23-32-12 | D05593J | 4 | | | D06666J | 3 | | | 276-299 |
| 201R | 24 | | PW | IA | 0-0 | 23-32-12 | D05593J | 3 | | | D06666J | 2 | | | 275-299 |
| 201Z | | | | IA | 0-0 | 23-32-12 | D05593J | 15 | | | D06666J | 1 | | | 275-299 |
| 202B | 24 | | PW | IB | 55-9 | 23-32-12 | D05593J | 7 | | | D06666J | 19 | | | 275 |
| 202B | 24 | | PW | IB | 55-11 | 23-32-12 | D05593J | 7 | | | D06666J | 19 | | | 276-299 |
| 202R | 24 | | PW | IB | 0-0 | 23-32-12 | D05593J | 6 | | | D06666J | 18 | | | 275-299 |
| 202Z | | | | IB | 0-0 | 23-32-12 | D05593J | | | FA | D06666J | | | FB | 275-299 |
| 203B | 24 | | PW | IC | 55-9 | 23-32-12 | D05593J | 9 | | | D06666J | 37 | | | 275 |
| 203B | 24 | | PW | IC | 55-11 | 23-32-12 | D05593J | 9 | | | D06666J | 37 | | | 276-299 |
| 203R | 24 | | PW | IC | 0-0 | 23-32-12 | D05593J | 8 | | | D06666J | 20 | | | 275-299 |
| 203Z | | | | IC | 0-0 | 23-32-12 | D05593J | | | FA | D06666J | | | FB | 275-299 |
| 204B | 24 | | PW | ID | 55-9 | 23-32-12 | D05593J | 11 | | | D06666J | 15 | | | 275 |
| 204B | 24 | | PW | ID | 55-11 | 23-32-12 | D05593J | 11 | | | D06666J | 15 | | | 276-299 |
| 204R | 24 | | PW | ID | 0-0 | 23-32-12 | D05593J | 10 | | | D06666J | 14 | | | 275-299 |
| 204Z | | | | ID | 0-0 | 23-32-12 | D05593J | | | FC | D06666J | | | FD | 275-299 |
| 205B | 24 | | PW | IE | 55-9 | 23-32-12 | D05593J | 13 | | | D06666J | 31 | | | 275 |
| 205B | 24 | | PW | IE | 55-11 | 23-32-12 | D05593J | 13 | | | D06666J | 31 | | | 276-299 |
| 205R | 24 | | PW | IE | 0-0 | 23-32-12 | D05593J | 12 | | | D06666J | 30 | | | 275-299 |
| 205Z | | | | IE | 0-0 | 23-32-12 | D05593J | | | FC | D06666J | | | FD | 275-299 |
| 206B | 24 | | PW | IF | 55-9 | 23-32-12 | D05593J | 21 | | | D06666J | 33 | | | 275 |
| 206B | 24 | | PW | IF | 55-11 | 23-32-12 | D05593J | 21 | | | D06666J | 33 | | | 276-299 |
| 206R | 24 | | PW | IF | 0-0 | 23-32-12 | D05593J | 20 | | | D06666J | 17 | | | 275-299 |
| 206Z | | | | IF | 0-0 | 23-32-12 | D05593J | | | FE | D06666J | | | FF | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1400
Page 2
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|-------|---|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1407 | 286T1407 | | | | VIDEO SYSTEM-FROM E2-5 TO VIDEO CONTROL CENTER (continued) | | | | | | | | | | | |
| 207B | 24 | PW | IG | 55-9 | 23-32-12 | D05593J | | 23 | | | | D06666J | 35 | | | 275 |
| 207B | 24 | PW | IG | 55-11 | 23-32-12 | D05593J | | 23 | | | | D06666J | 35 | | | 276-299 |
| 207R | 24 | PW | IG | 0-0 | 23-32-12 | D05593J | | 22 | | | | D06666J | 34 | | | 275-299 |
| 207Z | | | IG | 0-0 | 23-32-12 | D05593J | | | | FE | | D06666J | | | FF | 275-299 |
| FRA | | | | 0-0 | 23-32-12 | D06035J | | | | FA | | D06035J | 15 | | | 050-099 |
| FRA | | | | 0-0 | 23-32-12 | D06035J | | 15 | | | | D06035J | | | FA | 150-199 |
| FRA | | | | 0-0 | 23-32-12 | D05593J | | | | FA | | D05593J | 16 | | | 275-299 |
| FRB | | | | 0-0 | 23-32-12 | D06666J | | 38 | | | | D06666J | | | FB | 275-299 |
| FRC | | | | 0-0 | 23-32-12 | D05593J | | 24 | | | | D05593J | | | FC | 275-299 |
| FRD | | | | 0-0 | 23-32-12 | D06666J | | 32 | | | | D06666J | | | FD | 275-299 |
| FRE | | | | 0-0 | 23-32-12 | D05593J | | 19 | | | | D05593J | | | FE | 275-299 |
| FRF | | | | 0-0 | 23-32-12 | D06666J | | 16 | | | | D06666J | | | FF | 275-299 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|---|-------------|----|----|-------------|-------|----------|---------|------|------|--------|---------|-------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1413 286T1413 VIDEO SYSTEM-COAX CABLE ANTENNA COUPLER | | | | | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-32-13 | D05801J | = C1 | | | D01219 | = C1 | | | ALL |
| 01CX | | | | BR A | 36-2 | 23-32-13 | D05801J | = A1 | | | D01219 | = A1 | | | 050-099, 150-154, 162-164, 275-276 |
| 01CX | | | | 66 A | 36-2 | 23-32-13 | D05801J | = A1 | | | D01219 | = A1 | | | 155-157, 165-199, 277-299 |
| W1415 286T1415 VIDEO SYSTEM-ANTENNA COUPLER | | | | | | | | | | | | | | | |
| 002 | 18 | | | UA | 1-5 | 23-32-13 | D01221 | 2 | DK | | GD00255 | D.. | N | | ALL |
| 401B | 20 | | | UD A | 36-4 | 23-32-13 | D01221 | 4 | | | D05599J | 4 | | | ALL |
| 401G | 20 | | | UD A | 0-0 | 23-32-13 | D01221 | 3 | | | D05599J | 3 | | | ALL |
| 401R | 20 | | | UD A | 0-0 | 23-32-13 | D01221 | 1 | | | D05599J | 1 | | | ALL |
| 401Y | 20 | | | UD A | 0-0 | 23-32-13 | D01221 | 5 | | | D05599J | 5 | | | ALL |
| W1417 286T1417 VIDEO SYSTEM-FROM P37 TO FWD,MID,AFT PROJECTOR AND VIDEO CENTER | | | | | | | | | | | | | | | |
| 001 | 20 | | | PA | 35-0 | 23-32-11 | D05561P | 1 | | | D06037J | 1 | | | 050-099 |
| 001 | 20 | | | PA | 36-0 | 23-32-11 | D05561P | 1 | | | D06037J | 1 | | | 150-199 |
| 001 | 20 | | | PA | 52-0 | 23-32-11 | D05561P | 1 | | | D06668J | 26 | | | 275-278 |
| 001 | 20 | | | PA | 49-5 | 23-32-11 | D05561P | 1 | | | D06668J | 26 | | | 280-299 |
| 002 | 20 | | | PA | 46-0 | 23-32-11 | D05561P | 2 | | | D02031 | 1 | | | 050-099, 150-199 |
| 003 | 20 | | | PA | 77-0 | 23-32-11 | D05561P | 3 | | | SM00001 | | S | | 050-099 |
| 003 | 20 | | | PA | 65-0 | 23-32-11 | D05561P | 3 | | | D02245 | 1 | | | 150-199 |
| 004 | 20 | | | PA | 99-0 | 23-32-11 | D05561P | 4 | | | D01231 | 1 | | | 050-099 |
| 004 | 20 | | | PA | 107-0 | 23-32-11 | D05561P | 4 | | | D02043 | 1 | | | 150-199 |
| 005 | 20 | | | PA | 5-0 | 23-32-11 | D06037J | 2 | | | GD06733 | A.. | 2 | | 050-099, 150-199 |
| 005 | 20 | | | PA | 7-0 | 23-32-11 | D06668J | 42 | | | GD00434 | A.. | 2 | | 275-278 |
| 005 | 20 | | | PA | 4-4 | 23-32-11 | D06668J | 42 | | | GD00434 | A.. | 2 | | 280-299 |
| 006 | 20 | | | PA | 5-0 | 23-32-11 | D06037J | 3 | | | GD06733 | D.. | 2 | | 050-099, 150-199 |
| 007 | 20 | | | PA | 5-0 | 23-32-11 | D06037J | 4 | | | GD06733 | S.. | 2 | | 050-099, 150-199 |
| 007 | 20 | | | PA | 7-0 | 23-32-11 | D06668J | 38 | | | GD00434 | S.. | 2 | | 275-278 |
| 007 | 20 | | | PA | 4-4 | 23-32-11 | D06668J | 38 | | | GD00434 | S.. | 2 | | 280-299 |
| 008 | 20 | | | PA | 3-0 | 23-32-11 | D02031 | 4 | | | GD00743 | A.. | E | | 050-099, 150-199 |
| 009 | 20 | | | PA | 12-0 | 23-32-11 | SM00002 | | S | | GD01930 | A.. | 2 | | 050-099 |
| 009 | 20 | | | PA | 3-0 | 23-32-11 | D02245 | 4 | | | GD06727 | A.. | E | | 150-199 |
| 010 | 20 | | | PA | 12-0 | 23-32-11 | D01231 | 4 | | | GD01750 | A.. | 2 | | 050-099 |
| 010 | 20 | | | PA | 3-0 | 23-32-11 | D02043 | 4 | | | GD00749 | A.. | E | | 150-199 |
| 017 | 24 | | | PK | 33-0 | 23-32-13 | D02031 | 6 | | | D06037J | 5 | | | 050-099, 150-199 |
| 018 | 24 | | | PK | 33-0 | 23-32-13 | D02031 | 7 | | | D06037J | 6 | | | 050-099, 150-199 |
| 019 | 24 | | | PK | 33-0 | 23-32-13 | D02031 | 8 | | | D06037J | 7 | | | 050-099, 150-199 |
| 01CO | | | | A | 0-0 | 23-32-13 | D02033 | = C1 | | | D06037J | = C19 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1410

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|---|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1417 | 286T1417 | | | VIDEO SYSTEM-FROM P37 TO FWD,MID,AFT PROJECTOR AND VIDEO CENTER (continued) | | | | | | | | | | | | | |
| 01CX | | | 5X | A | 32-0 | 23-32-13 | D02033 | = A1 | | | | | D06037J | 19 | | | 050-099 |
| 01CX | | | 5X | A | 33-0 | 23-32-13 | D02033 | = A1 | | | | | D06037J | 19 | | | 150-199 |
| 020 | 20 | | PA | | 33-0 | 23-32-13 | D02031 | 2 | | | | | D06037J | 8 | | | 050-099, 150-199 |
| 021 | 20 | | PA | | 3-0 | 23-32-13 | D02031 | 3 | | | | | GD00745 | D.. | E | | 050-099, 150-199 |
| 022 | 20 | | PA | | 3-0 | 23-32-13 | D02031 | 5 | | | | | GD00747 | S.. | E | | 050-099, 150-199 |
| 023 | 24 | | PK | | 64-0 | 23-32-13 | SM00003 | | S | | | | D06037J | 9 | | | 050-099 |
| 023 | 24 | | PK | | 58-0 | 23-32-13 | D02245 | 6 | | | | | D06037J | 9 | | | 150-199 |
| 024 | 24 | | PK | | 64-0 | 23-32-13 | SM00004 | | S | | | | D06037J | 10 | | | 050-099 |
| 024 | 24 | | PK | | 58-0 | 23-32-13 | D02245 | 7 | | | | | D06037J | 10 | | | 150-199 |
| 025 | 24 | | PK | | 64-0 | 23-32-13 | SM00005 | | S | | | | D06037J | 11 | | | 050-099 |
| 025 | 24 | | PK | | 58-0 | 23-32-13 | D02245 | 8 | | | | | D06037J | 11 | | | 150-199 |
| 026 | 20 | | PA | | 64-0 | 23-32-13 | SM00006 | | S | | | | D06037J | 12 | | | 050-099 |
| 026 | 20 | | PA | | 58-0 | 23-32-13 | D02245 | 2 | | | | | D06037J | 12 | | | 150-199 |
| 027 | 20 | | PA | | 12-0 | 23-32-13 | SM00007 | | S | | | | GD01930 | D.. | 2 | | 050-099 |
| 027 | 20 | | PA | | 3-0 | 23-32-13 | D02245 | 3 | | | | | GD06729 | D.. | E | | 150-199 |
| 028 | 20 | | PA | | 12-0 | 23-32-13 | SM00008 | | S | | | | GD01930 | S.. | 2 | | 050-099 |
| 028 | 20 | | PA | | 3-0 | 23-32-13 | D02245 | 5 | | | | | GD06731 | S.. | E | | 150-199 |
| 029 | 24 | | PK | | 85-0 | 23-32-13 | D01231 | 6 | | | | | D06037J | 13 | | | 050-099 |
| 029 | 24 | | PK | | 93-0 | 23-32-13 | D02043 | 6 | | | | | D06037J | 13 | | | 150-199 |
| 02CO | | | | B | 0-0 | 23-32-13 | D09019P | = C1 | | | | | D06037J | = C23 | | | 050-099 |
| 02CO | | | | B | 0-0 | 23-32-13 | D02247 | = C1 | | | | | D06037J | = C23 | | | 150-199 |
| 02CX | | | 5X | B | 63-0 | 23-32-13 | D09019P | = A1 | | | | | D06037J | 23 | | | 050-099 |
| 02CX | | | 5X | B | 52-0 | 23-32-13 | D02247 | = A1 | | | | | D06037J | 23 | | | 150-199 |
| 030 | 24 | | PK | | 85-0 | 23-32-13 | D01231 | 7 | | | | | D06037J | 14 | | | 050-099 |
| 030 | 24 | | PK | | 93-0 | 23-32-13 | D02043 | 7 | | | | | D06037J | 14 | | | 150-199 |
| 031 | 24 | | PK | | 85-0 | 23-32-13 | D01231 | 8 | | | | | D06037J | 16 | | | 050-099 |
| 031 | 24 | | PK | | 93-0 | 23-32-13 | D02043 | 8 | | | | | D06037J | 16 | | | 150-199 |
| 032 | 20 | | PA | | 85-0 | 23-32-13 | D01231 | 2 | | | | | D06037J | 17 | | | 050-099 |
| 032 | 20 | | PA | | 93-0 | 23-32-13 | D02043 | 2 | | | | | D06037J | 17 | | | 150-199 |
| 033 | 20 | | PA | | 12-0 | 23-32-13 | D01231 | 3 | | | | | GD01750 | D.. | 2 | | 050-099 |
| 033 | 20 | | PA | | 3-0 | 23-32-13 | D02043 | 3 | | | | | GD00751 | D.. | E | | 150-199 |
| 034 | 20 | | PA | | 12-0 | 23-32-13 | D01231 | 5 | | | | | GD01750 | S.. | 2 | | 050-099 |
| 034 | 20 | | PA | | 3-0 | 23-32-13 | D02043 | 5 | | | | | GD00753 | S.. | E | | 150-199 |
| 03CO | | | | C | 0-0 | 23-32-13 | D01233 | = C1 | | | | | D06037J | = C27 | | | 050-099 |
| 03CO | | | | C | 0-0 | 23-32-13 | D02045 | = C1 | | | | | D06037J | = C27 | | | 150-199 |
| 03CX | | | 5X | C | 85-0 | 23-32-13 | D01233 | = A1 | | | | | D06037J | 27 | | | 050-099 |
| 03CX | | | 5X | C | 90-0 | 23-32-13 | D02045 | = A1 | | | | | D06037J | 27 | | | 150-199 |
| 04CO | | | | D | 0-0 | 23-32-13 | D02231 | = C1 | | | | | D09019J | = C1 | | | 050-099 |
| 04CX | | | 5X | D | 63-0 | 23-32-13 | D02231 | = A1 | | | | | D09019J | = A1 | | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1410

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | Effectivity | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|-------------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1417 | 286T1417 | | | VIDEO SYSTEM-FROM P37 TO FWD,MID,AFT PROJECTOR AND VIDEO CENTER (continued) | | | | | | | | | | | |
| 09CO | | | | I | 0-0 | 23-32-21 | D06037J | = | C15 | | D04571J | = | C15 | | 050-099 |
| 09CO | | | | I | 0-0 | 23-32-21 | D04571J | = | C15 | | D06037J | = | C15 | | 150-199 |
| 09CO | | | | F | 0-0 | 23-32-21 | D04571J | = | C15 | | D06099J | = | C15 | | 275-299 |
| 09CX | | 5X | | I | 40-0 | 23-32-21 | D06037J | | 15 | | D04571J | | 15 | | 050-099 |
| 09CX | | 5X | | I | 40-0 | 23-32-21 | D04571J | | 15 | | D06037J | | 15 | | 150-199 |
| 09CX | | 5X | | F | 56-0 | 23-32-21 | D04571J | | 15 | | D06099J | | 15 | | 275-278 |
| 09CX | | 5X | | F | 53-9 | 23-32-21 | D04571J | | 15 | | D06099J | | 15 | | 280-299 |
| 125 | 18 | PA | | | 30-0 | 23-32-31 | D05561P | | 5 | DL | SM00012 | | | S | 275-276 |
| 126 | 20 | PA | | | 0-6 | 23-32-31 | SM00017 | | | 9 | D02323 | | 12 | | 275-299 |
| 127 | 20 | PA | | | 4-0 | 23-32-31 | GD06867 | | S.. | E | D02323 | | 13 | | 275-278 |
| 127 | 20 | PA | | | 3-3 | 23-32-31 | GD06867 | | S.. | E | D02323 | | 13 | | 280-299 |
| 131 | 18 | PA | | | 67-0 | 23-32-41 | D05561P | | 6 | DL | SM00013 | | | S | 275-276 |
| 132 | 20 | PA | | | 0-6 | 23-32-41 | SM00019 | | | 9 | D02361 | | 12 | | 275-299 |
| 133 | 20 | PA | | | 4-0 | 23-32-41 | GD06871 | | S.. | E | D02361 | | 13 | | 275-278 |
| 133 | 20 | PA | | | 2-6 | 23-32-41 | GD06871 | | S.. | E | D02361 | | 13 | | 280-299 |
| 136 | 20 | PA | | | 0-6 | 23-32-51 | SM00020 | | | 9 | D02391 | | 11 | | 275-299 |
| 137 | 18 | PA | | | 92-0 | 23-32-51 | D05561P | | 7 | DL | SM00014 | | | S | 275-276 |
| 138 | 20 | PA | | | 0-6 | 23-32-51 | SM00021 | | | 9 | D02391 | | 12 | | 275-299 |
| 139 | 20 | PA | | | 3-0 | 23-32-51 | GD06875 | | S.. | E | D02391 | | 13 | | 275-278 |
| 139 | 20 | PA | | | 2-11 | 23-32-51 | GD06875 | | S.. | E | D02391 | | 13 | | 280-299 |
| 140 | 20 | PA | | | 0-6 | 23-32-31 | SM00016 | | | 9 | D02323 | | 11 | | 275-299 |
| 141 | 20 | PA | | | 0-6 | 23-32-41 | SM00018 | | | 9 | D02361 | | 11 | | 275-299 |
| 142 | 20 | PA | | | 0-6 | 23-32-61 | SM00022 | | | 9 | D02433 | | 11 | | 275-299 |
| 143 | 18 | PA | | | 131-0 | 23-32-61 | D05561P | | 8 | DL | SM00015 | | | S | 275-276 |
| 144 | 20 | PA | | | 0-6 | 23-32-61 | SM00023 | | | 9 | D02433 | | 12 | | 275-299 |
| 145 | 20 | PA | | | 4-0 | 23-32-61 | GD06879 | | S.. | E | D02433 | | 13 | | 275-278 |
| 145 | 20 | PA | | | 3-5 | 23-32-61 | GD06879 | | S.. | E | D02433 | | 13 | | 280-299 |
| 151 | 20 | UA | | | 4-0 | 23-32-31 | SM00017 | REF | | FF | GD06867 | S.. | E | | 275-276 |
| 151 | 20 | UA | | | 4-0 | 23-32-31 | GD06867 | S.. | E | | SM00017 | REF | | FF | 277-278 |
| 151 | 20 | UA | | | 3-3 | 23-32-31 | GD06867 | S.. | E | | SM00017 | REF | | FF | 280-299 |
| 152 | 20 | UA | | | 35-0 | 23-32-31 | SM00012 | REF | | FE | GD06905 | A.. | E | *1 | 275-276 |
| 153 | 20 | UA | | | 4-0 | 23-32-41 | SM00019 | REF | | FH | GD06871 | S.. | E | | 275-276 |
| 153 | 20 | UA | | | 4-0 | 23-32-41 | GD06871 | S.. | E | | SM00019 | REF | | FH | 277-278 |
| 153 | 20 | UA | | | 2-6 | 23-32-41 | GD06871 | S.. | E | | SM00019 | REF | | FH | 280-299 |
| 154 | 20 | UA | | | 70-0 | 23-32-41 | SM00013 | REF | | FG | GD06905 | A.. | E | *2 | 275-276 |
| 155 | 20 | UA | | | 4-0 | 23-32-51 | SM00021 | REF | | FJ | GD06875 | S.. | E | | 275-276 |
| 155 | 20 | UA | | | 4-0 | 23-32-51 | GD06875 | S.. | E | | SM00021 | REF | | FJ | 277-278 |
| 155 | 20 | UA | | | 2-11 | 23-32-51 | GD06875 | S.. | E | | SM00021 | REF | | FJ | 280-299 |
| 156 | 20 | UA | | | 96-0 | 23-32-51 | SM00014 | REF | | FI | GD06905 | A.. | E | *3 | 275-276 |

WIRE LIST
D280T132

91-21-11
Section W1410
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1417 | 286T1417 | | | VIDEO SYSTEM-FROM P37 TO FWD,MID,AFT PROJECTOR AND VIDEO CENTER (continued) | | | | | | | | | | | | |
| 157 | 20 | | UA | 4-0 | 23-32-61 | SM00023 | | REF | | FL | GD06879 | S.. | E | | 275-276 | |
| 157 | 20 | | UA | 4-0 | 23-32-61 | GD06879 | | S.. | E | | SM00023 | REF | | FL | 277-278 | |
| 157 | 20 | | UA | 2-11 | 23-32-61 | GD06879 | | S.. | E | | SM00023 | REF | | FL | 280-299 | |
| 158 | 20 | | UA | 135-0 | 23-32-61 | SM00015 | | REF | | FK | GD06905 | A.. | E | *4 | 275-276 | |
| 206B | 24 | | PW | IF | 40-0 | 23-32-21 | D04571J | | 2 | | D06039J | 22 | | | 050-099, 150-199 | |
| 206B | 24 | | PW | IF | 57-0 | 23-32-21 | D04571J | | 2 | | D06099J | 2 | | | 275-278 | |
| 206B | 24 | | PW | IF | 54-9 | 23-32-21 | D04571J | | 2 | | D06099J | 2 | | | 280-299 | |
| 206R | 24 | | PW | IF | 0-0 | 23-32-21 | D04571J | | 1 | | D06039J | 20 | | | 050-099, 150-199 | |
| 206R | 24 | | PW | IF | 0-0 | 23-32-21 | D04571J | | 1 | | D06099J | 1 | | | 275-299 | |
| 206Z | | | | IF | 0-0 | 23-32-21 | D04571J | | | FA | D06039J | | | FB | 050-099 | |
| 206Z | | | | IF | 0-0 | 23-32-21 | D04571J | | | FD | D06039J | | | FC | 150-199 | |
| 206Z | | | | IF | 0-0 | 23-32-21 | D04571J | | | FD | D06099J | | | FC | 275-299 | |
| 207B | 24 | | PW | IG | 40-0 | 23-32-21 | D04571J | | 4 | | D06039J | 25 | | | 050-099, 150-199 | |
| 207B | 24 | | PW | IG | 57-0 | 23-32-21 | D04571J | | 4 | | D06099J | 4 | | | 275-278 | |
| 207B | 24 | | PW | IG | 54-9 | 23-32-21 | D04571J | | 4 | | D06099J | 4 | | | 280-299 | |
| 207R | 24 | | PW | IG | 0-0 | 23-32-21 | D04571J | | 3 | | D06039J | 24 | | | 050-099, 150-199 | |
| 207R | 24 | | PW | IG | 0-0 | 23-32-21 | D04571J | | 3 | | D06099J | 3 | | | 275-299 | |
| 207Z | | | | IG | 0-0 | 23-32-21 | D04571J | | | FA | D06039J | | | FB | 050-099 | |
| 207Z | | | | IG | 0-0 | 23-32-21 | D04571J | | | FD | D06039J | | | FC | 150-199 | |
| 207Z | | | | IG | 0-0 | 23-32-21 | D04571J | | | FD | D06099J | | | FC | 275-299 | |
| 208B | 24 | | PW | IH | 40-0 | 23-32-21 | D04571J | | 12 | | D06039J | 34 | | | 050-099, 150-199 | |
| 208B | 24 | | PW | IH | 57-0 | 23-32-21 | D04571J | | 12 | | D06099J | 12 | | | 275-278 | |
| 208B | 24 | | PW | IH | 54-9 | 23-32-21 | D04571J | | 12 | | D06099J | 12 | | | 280-299 | |
| 208R | 24 | | PW | IH | 0-0 | 23-32-21 | D04571J | | 11 | | D06039J | 33 | | | 050-099, 150-199 | |
| 208R | 24 | | PW | IH | 0-0 | 23-32-21 | D04571J | | 11 | | D06099J | 11 | | | 275-299 | |
| 208Z | | | | IH | 0-0 | 23-32-21 | D04571J | | | FA | D06039J | | | FB | 050-099 | |
| 208Z | | | | IH | 0-0 | 23-32-21 | D04571J | | | FD | D06039J | | | FC | 150-199 | |
| 208Z | | | | IH | 0-0 | 23-32-21 | D04571J | | | FD | D06099J | | | FC | 275-299 | |
| 209B | 24 | | PW | II | 34-0 | 23-32-31 | D06668J | | 2 | | D02323 | 8 | | | 275-278 | |
| 209B | 24 | | PW | II | 30-8 | 23-32-31 | D06668J | | 2 | | D02323 | 8 | | | 280-299 | |
| 209R | 24 | | PW | II | 0-0 | 23-32-31 | D06668J | | 1 | | D02323 | 7 | | | 275-299 | |
| 209Z | | | | II | 0-0 | 23-32-31 | D06668J | | 3 | | D02323 | 9 | | | 275-299 | |
| 210B | 24 | | 7P | IJ | 34-0 | 23-32-31 | D06668J | | 9 | | D02323 | 2 | | | 275-278 | |
| 210B | 24 | | 7P | IJ | 30-8 | 23-32-31 | D06668J | | 9 | | D02323 | 2 | | | 280-299 | |
| 210BN | 24 | | 7P | IJ | 0-0 | 23-32-31 | D06668J | | 8 | | D02323 | 1 | | | 275-299 | |
| 210Z | | | | IJ | 0-0 | 23-32-31 | D06668J | | 10 | | D02323 | 3 | | | 275-299 | |
| 211B | 24 | | 7P | IK | 34-0 | 23-32-31 | D06668J | | 16 | | D02323 | 5 | | | 275-278 | |
| 211B | 24 | | 7P | IK | 30-8 | 23-32-31 | D06668J | | 16 | | D02323 | 5 | | | 280-299 | |
| 211BN | 24 | | 7P | IK | 0-0 | 23-32-31 | D06668J | | 15 | | D02323 | 4 | | | 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W1410

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1417 | 286T1417 | | | VIDEO SYSTEM-FROM P37 TO FWD,MID,AFT PROJECTOR AND VIDEO CENTER (continued) | | | | | | | | | | | | |
| 211Z | | | | IK | 0-0 | 23-32-31 | D06668J | 17 | | | | D02323 | 6 | | | 275-299 |
| 212B | 24 | 7P | | IL | 34-0 | 23-32-31 | D06668J | 19 | | | | D02323 | 15 | | | 275-278 |
| 212B | 24 | 7P | | IL | 30-8 | 23-32-31 | D06668J | 19 | | | | D02323 | 15 | | | 280-299 |
| 212BN | 24 | 7P | | IL | 0-0 | 23-32-31 | D06668J | 18 | | | | D02323 | 14 | | | 275-299 |
| 212Z | | | | IL | 0-0 | 23-32-31 | D06668J | 20 | | | | D02323 | 16 | | | 275-299 |
| 214B | 18 | 8K | | IN | 35-0 | 23-32-31 | GD06905 | A.. | E | *1 | | SM00017 | 9 | | | 275-276 |
| 214B | 18 | 8K | | IN | 35-0 | 23-32-31 | D05561P | 9 | DL | | | SM00017 | 9 | | | 277-278 |
| 214B | 18 | 8K | | IN | 29-8 | 23-32-31 | D05561P | 9 | DL | | | SM00017 | 9 | | | 280-299 |
| 214R | 18 | 8K | | IN | 0-0 | 23-32-31 | SM00012 | | S | | | SM00016 | 9 | | | 275-276 |
| 214R | 18 | 8K | | IN | 0-0 | 23-32-31 | D05561P | 5 | DL | | | SM00016 | 9 | | | 277-299 |
| 214Z | | | | IN | 0-0 | 23-32-31 | SM00012 | REF | | FE | | SM00017 | REF | | FF | 275-276 |
| 214Z | | | | IN | 0-0 | 23-32-31 | D05561P | DED | | | | SM00017 | REF | | FF | 277-299 |
| 215B | 18 | 8K | | IO | 70-0 | 23-32-41 | GD06905 | A.. | E | *2 | | SM00019 | 9 | | | 275-276 |
| 215B | 18 | 8K | | IO | 70-0 | 23-32-41 | D05561P | 10 | DL | | | SM00019 | 9 | | | 277-278 |
| 215B | 18 | 8K | | IO | 67-5 | 23-32-41 | D05561P | 10 | DL | | | SM00019 | 9 | | | 280-299 |
| 215R | 18 | 8K | | IO | 0-0 | 23-32-41 | SM00013 | | S | | | SM00018 | 9 | | | 275-276 |
| 215R | 18 | 8K | | IO | 0-0 | 23-32-41 | D05561P | 6 | DL | | | SM00018 | 9 | | | 277-299 |
| 215Z | | | | IO | 0-0 | 23-32-41 | SM00013 | REF | | FG | | SM00019 | REF | | FH | 275-276 |
| 215Z | | | | IO | 0-0 | 23-32-41 | D05561P | DED | | | | SM00019 | REF | | FH | 277-299 |
| 216B | 18 | 8K | | IP | 96-0 | 23-32-51 | GD06905 | A.. | E | *3 | | SM00021 | 9 | | | 275-276 |
| 216B | 18 | 8K | | IP | 96-0 | 23-32-51 | D05561P | 11 | DL | | | SM00021 | 9 | | | 277-278 |
| 216B | 18 | 8K | | IP | 94-0 | 23-32-51 | D05561P | 11 | DL | | | SM00021 | 9 | | | 280-299 |
| 216R | 18 | 8K | | IP | 0-0 | 23-32-51 | SM00014 | | S | | | SM00020 | 9 | | | 275-276 |
| 216R | 18 | 8K | | IP | 0-0 | 23-32-51 | D05561P | 7 | DL | | | SM00020 | 9 | | | 277-299 |
| 216Z | | | | IP | 0-0 | 23-32-51 | SM00014 | REF | | FI | | SM00021 | REF | | FJ | 275-276 |
| 216Z | | | | IP | 0-0 | 23-32-51 | D05561P | DED | | | | SM00021 | REF | | FJ | 277-299 |
| 217B | 18 | 8K | | IQ | 136-0 | 23-32-61 | GD06905 | A.. | E | *4 | | SM00023 | 9 | | | 275-276 |
| 217B | 18 | 8K | | IQ | 136-0 | 23-32-61 | D05561P | 12 | DL | | | SM00023 | 9 | | | 277-278 |
| 217B | 18 | 8K | | IQ | 131-0 | 23-32-61 | D05561P | 12 | DL | | | SM00023 | 9 | | | 280-299 |
| 217R | 18 | 8K | | IQ | 0-0 | 23-32-61 | SM00015 | | S | | | SM00022 | 9 | | | 275-276 |
| 217R | 18 | 8K | | IQ | 0-0 | 23-32-61 | D05561P | 8 | DL | | | SM00022 | 9 | | | 277-299 |
| 217Z | | | | IQ | 0-0 | 23-32-61 | SM00015 | REF | | FK | | SM00023 | REF | | FL | 275-276 |
| 217Z | | | | IQ | 0-0 | 23-32-61 | D05561P | DED | | | | SM00023 | REF | | FL | 277-299 |
| 218B | 24 | PW | | IR | 48-0 | 23-32-41 | D02351 | 8 | | | | D02361 | 8 | | | 275-278 |
| 218B | 24 | PW | | IR | 47-6 | 23-32-41 | D02351 | 8 | | | | D02361 | 8 | | | 280-299 |
| 218R | 24 | PW | | IR | 0-0 | 23-32-41 | D02351 | 7 | | | | D02361 | 7 | | | 275-299 |
| 218Z | | | | IR | 0-0 | 23-32-41 | D02351 | 9 | | | | D02361 | 9 | | | 275-299 |
| 219B | 24 | 7P | | IS | 48-0 | 23-32-41 | D02351 | 2 | | | | D02361 | 2 | | | 275-278 |
| 219B | 24 | 7P | | IS | 47-6 | 23-32-41 | D02351 | 2 | | | | D02361 | 2 | | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1410

Page 5

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1417 | 286T1417 | | | VIDEO SYSTEM-FROM P37 TO FWD,MID,AFT PROJECTOR AND VIDEO CENTER (continued) | | | | | | | | | | | |
| 219BN | 24 | 7P | IS | 0-0 | 23-32-41 | D02351 | | 1 | | | D02361 | | 1 | | 275-299 |
| 219Z | | | IS | 0-0 | 23-32-41 | D02351 | | 3 | | | D02361 | | 3 | | 275-299 |
| 220B | 24 | 7P | IT | 48-0 | 23-32-41 | D02351 | | 5 | | | D02361 | | 5 | | 275-278 |
| 220B | 24 | 7P | IT | 47-6 | 23-32-41 | D02351 | | 5 | | | D02361 | | 5 | | 280-299 |
| 220BN | 24 | 7P | IT | 0-0 | 23-32-41 | D02351 | | 4 | | | D02361 | | 4 | | 275-299 |
| 220Z | | | IT | 0-0 | 23-32-41 | D02351 | | 6 | | | D02361 | | 6 | | 275-299 |
| 221B | 24 | 7P | IU | 48-0 | 23-32-41 | D02351 | | 15 | | | D02361 | | 15 | | 275-278 |
| 221B | 24 | 7P | IU | 47-6 | 23-32-41 | D02351 | | 15 | | | D02361 | | 15 | | 280-299 |
| 221BN | 24 | 7P | IU | 0-0 | 23-32-41 | D02351 | | 14 | | | D02361 | | 14 | | 275-299 |
| 221Z | | | IU | 0-0 | 23-32-41 | D02351 | | 16 | | | D02361 | | 16 | | 275-299 |
| 226B | 24 | PW | JA | 95-0 | 23-32-51 | D06668J | | 44 | | | D02391 | | 8 | | 275-278 |
| 226B | 24 | PW | JA | 94-11 | 23-32-51 | D06668J | | 44 | | | D02391 | | 8 | | 280-299 |
| 226R | 24 | PW | JA | 0-0 | 23-32-51 | D06668J | | 43 | | | D02391 | | 7 | | 275-299 |
| 226Z | | | JA | 0-0 | 23-32-51 | D06668J | | 45 | | | D02391 | | 9 | | 275-299 |
| 227B | 24 | 7P | JB | 95-0 | 23-32-51 | D06668J | | 47 | | | D02391 | | 2 | | 275-278 |
| 227B | 24 | 7P | JB | 94-11 | 23-32-51 | D06668J | | 47 | | | D02391 | | 2 | | 280-299 |
| 227BN | 24 | 7P | JB | 0-0 | 23-32-51 | D06668J | | 46 | | | D02391 | | 1 | | 275-299 |
| 227Z | | | JB | 0-0 | 23-32-51 | D06668J | | 48 | | | D02391 | | 3 | | 275-299 |
| 228B | 24 | 7P | JC | 95-0 | 23-32-51 | D06668J | | 50 | | | D02391 | | 5 | | 275-278 |
| 228B | 24 | 7P | JC | 94-11 | 23-32-51 | D06668J | | 50 | | | D02391 | | 5 | | 280-299 |
| 228BN | 24 | 7P | JC | 0-0 | 23-32-51 | D06668J | | 49 | | | D02391 | | 4 | | 275-299 |
| 228Z | | | JC | 0-0 | 23-32-51 | D06668J | | 51 | | | D02391 | | 6 | | 275-299 |
| 229B | 24 | 7P | JD | 95-0 | 23-32-51 | D06668J | | 53 | | | D02391 | | 15 | | 275-278 |
| 229B | 24 | 7P | JD | 94-11 | 23-32-51 | D06668J | | 53 | | | D02391 | | 15 | | 280-299 |
| 229BN | 24 | 7P | JD | 0-0 | 23-32-51 | D06668J | | 52 | | | D02391 | | 14 | | 275-299 |
| 229Z | | | JD | 0-0 | 23-32-51 | D06668J | | 54 | | | D02391 | | 16 | | 275-299 |
| 235B | 24 | PW | JJ | 50-0 | 23-32-61 | D02413 | | 8 | | | D02433 | | 8 | | 275-278 |
| 235B | 24 | PW | JJ | 51-11 | 23-32-61 | D02413 | | 8 | | | D02433 | | 8 | | 280-299 |
| 235R | 24 | PW | JJ | 0-0 | 23-32-61 | D02413 | | 7 | | | D02433 | | 7 | | 275-299 |
| 235Z | | | JJ | 0-0 | 23-32-61 | D02413 | | 9 | | | D02433 | | 9 | | 275-299 |
| 236B | 24 | 7P | JK | 50-0 | 23-32-61 | D02413 | | 2 | | | D02433 | | 2 | | 275-278 |
| 236B | 24 | 7P | JK | 51-11 | 23-32-61 | D02413 | | 2 | | | D02433 | | 2 | | 280-299 |
| 236BN | 24 | 7P | JK | 0-0 | 23-32-61 | D02413 | | 1 | | | D02433 | | 1 | | 275-299 |
| 236Z | | | JK | 0-0 | 23-32-61 | D02413 | | 3 | | | D02433 | | 3 | | 275-299 |
| 237B | 24 | 7P | JL | 50-0 | 23-32-61 | D02413 | | 5 | | | D02433 | | 5 | | 275-278 |
| 237B | 24 | 7P | JL | 51-11 | 23-32-61 | D02413 | | 5 | | | D02433 | | 5 | | 280-299 |
| 237BN | 24 | 7P | JL | 0-0 | 23-32-61 | D02413 | | 4 | | | D02433 | | 4 | | 275-299 |
| 237Z | | | JL | 0-0 | 23-32-61 | D02413 | | 6 | | | D02433 | | 6 | | 275-299 |
| 238B | 24 | 7P | JM | 50-0 | 23-32-61 | D02413 | | 15 | | | D02433 | | 15 | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W1410

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1417 | 286T1417 | | | VIDEO SYSTEM-FROM P37 TO FWD,MID,AFT PROJECTOR AND VIDEO CENTER (continued) | | | | | | | | | | | |
| 238B | 24 | 7P | JM | 51-11 | 23-32-61 | D02413 | | 15 | | | D02433 | 15 | | | 280-299 |
| 238BN | 24 | 7P | JM | 0-0 | 23-32-61 | D02413 | | 14 | | | D02433 | 14 | | | 275-299 |
| 238Z | | | JM | 0-0 | 23-32-61 | D02413 | | 16 | | | D02433 | 16 | | | 275-299 |
| 301B | 24 | PX | MA | 40-0 | 23-32-21 | D04571J | | 5 | | | D06039J | 27 | | | 050-099, 150-199 |
| 301B | 24 | PX | MA | 57-0 | 23-32-21 | D04571J | | 5 | | | D06099J | 5 | | | 275-278 |
| 301B | 24 | PX | MA | 54-9 | 23-32-21 | D04571J | | 5 | | | D06099J | 5 | | | 280-299 |
| 301R | 24 | PX | MA | 0-0 | 23-32-21 | D04571J | | 6 | | | D06039J | 28 | | | 050-099, 150-199 |
| 301R | 24 | PX | MA | 0-0 | 23-32-21 | D04571J | | 6 | | | D06099J | 6 | | | 275-299 |
| 301Y | 24 | PX | MA | 0-0 | 23-32-21 | D04571J | | 7 | | | D06039J | 29 | | | 050-099, 150-199 |
| 301Y | 24 | PX | MA | 0-0 | 23-32-21 | D04571J | | 7 | | | D06099J | 7 | | | 275-299 |
| 301Z | | | MA | 0-0 | 23-32-21 | D04571J | | | | FA | D06039J | | | FB | 050-099 |
| 301Z | | | MA | 0-0 | 23-32-21 | D04571J | | | | FD | D06039J | | | FC | 150-199 |
| 301Z | | | MA | 0-0 | 23-32-21 | D04571J | | | | FD | D06099J | | | FC | 275-299 |
| 302B | 24 | PX | MB | 40-0 | 23-32-21 | D04571J | | 8 | | | D06039J | 30 | | | 050-099, 150-199 |
| 302B | 24 | PX | MB | 57-0 | 23-32-21 | D04571J | | 8 | | | D06099J | 8 | | | 275-278 |
| 302B | 24 | PX | MB | 54-9 | 23-32-21 | D04571J | | 8 | | | D06099J | 8 | | | 280-299 |
| 302R | 24 | PX | MB | 0-0 | 23-32-21 | D04571J | | 9 | | | D06039J | 31 | | | 050-099, 150-199 |
| 302R | 24 | PX | MB | 0-0 | 23-32-21 | D04571J | | 9 | | | D06099J | 9 | | | 275-299 |
| 302Y | 24 | PX | MB | 0-0 | 23-32-21 | D04571J | | 10 | | | D06039J | 32 | | | 050-099, 150-199 |
| 302Y | 24 | PX | MB | 0-0 | 23-32-21 | D04571J | | 10 | | | D06099J | 10 | | | 275-299 |
| 302Z | | | MB | 0-0 | 23-32-21 | D04571J | | | | FA | D06039J | | | FB | 050-099 |
| 302Z | | | MB | 0-0 | 23-32-21 | D04571J | | | | FD | D06039J | | | FC | 150-199 |
| 302Z | | | MB | 0-0 | 23-32-21 | D04571J | | | | FD | D06099J | | | FC | 275-299 |
| 401B | 20 | PD | QA | 112-0 | 23-32-13 | D06037J | | 21 | | | D05599P | 4 | | | 050-099 |
| 401B | 20 | PD | QA | 140-0 | 23-32-13 | D06037J | | 21 | | | D05599P | 4 | | | 150-199 |
| 401B | 20 | PD | QA | 150-0 | 23-32-13 | D06668J | | 36 | | | D05599P | 4 | | | 275-278 |
| 401B | 20 | PD | QA | 147-8 | 23-32-13 | D06668J | | 36 | | | D05599P | 4 | | | 280-299 |
| 401G | 20 | PD | QA | 0-0 | 23-32-13 | D06037J | | 18 | | | D05599P | 3 | | | 050-099, 150-199 |
| 401G | 20 | PD | QA | 0-0 | 23-32-13 | D06668J | | 34 | | | D05599P | 3 | | | 275-299 |
| 401R | 20 | PD | QA | 0-0 | 23-32-13 | D06037J | | 22 | | | D05599P | 1 | | | 050-099, 150-199 |
| 401R | 20 | PD | QA | 0-0 | 23-32-13 | D06668J | | 37 | | | D05599P | 1 | | | 275-299 |
| 401Y | 20 | PD | QA | 0-0 | 23-32-13 | D06037J | | 20 | | | D05599P | 5 | | | 050-099, 150-199 |
| 401Y | 20 | PD | QA | 0-0 | 23-32-13 | D06668J | | 35 | | | D05599P | 5 | | | 275-299 |
| 501 | 20 | PA | | 10-0 | 23-32-21 | D04571J | | 26 | | | SP00429 | | S | | 050-099 |
| 501 | 20 | PA | | 18-0 | 23-32-21 | SP00003 | | | 9 | | SP00429 | | S | | 150, 152-199 |
| 501 | 20 | PA | | 18-0 | 23-32-21 | D04571J | | 26 | | | SP00429 | | S | | 151, 275-278 |
| 501 | 20 | PA | | 17-5 | 23-32-21 | D04571J | | 26 | | | SP00429 | | S | | 280-299 |
| 502 | 20 | PA | | 5-0 | 23-32-11 | D06037J | | 24 | | | GD06733 | A.. | 2 | | 050-099, 150-199 |
| 617 | 20 | PA | | 4-6 | 23-32-21 | D06099J | | 13 | | | GD00434 | S.. | 2 | | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W1410
Page 7
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-----|-------------|----|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W1417 | 286T1417 | | | VIDEO SYSTEM-FROM P37 TO FWD,MID,AFT PROJECTOR AND VIDEO CENTER (continued) | | | | | | | | | | | | | | |
| 900 | 20 | | PA | | 10-0 | 23-32-21 | SP00003 | | | | 9 | | | D06039J | 1 | | | 150, 152-199 |
| 901 | 20 | | PQ | AN | 10-0 | 23-32-21 | SP00001 | | | | 9 | | | D04571J | 14 | | | 150, 152-199 |
| 901Z | | | | AN | 0-0 | 23-32-21 | SP00001 | | | DED | 9 | | | D04571J | 13 | | | 150, 152-199 |
| 902 | 20 | | PQ | AO | 10-0 | 23-32-21 | SP00002 | | | | S | | | D04571J | 16 | | | 150, 152-199 |
| 902Z | | | | AO | 0-0 | 23-32-21 | SP00002 | | | | S | | FM | D04571J | DED | | | 150, 152-199 |
| 903 | 20 | | PA | | 20-0 | 23-32-11 | D02233 | | | 1 | | | | SM00001 | | S | | 050-099 |
| 903 | 20 | | PA | | 3-0 | 23-32-21 | SP00002 | | | | S | | FM | GD02202 | S.. | 2 | | 150, 152-199 |
| 904 | 20 | | PA | | 3-0 | 23-32-21 | D06039J | | | 2 | | | | GD06733 | D.. | 2 | | 150, 152-199 |
| 905 | 20 | | PA | | 3-0 | 23-32-21 | D06039J | | | 3 | | | | GD06733 | D.. | 2 | | 150, 152-199 |
| 906 | 20 | | PA | | 3-0 | 23-32-21 | D06039J | | | 4 | | | | GD06733 | S.. | 2 | | 150, 152-199 |
| 907 | 20 | | PA | | 3-0 | 23-32-21 | D06039J | | | 8 | | | | GD06733 | A.. | 2 | | 150, 152-199 |
| 908 | 20 | | PA | | 3-0 | 23-32-21 | D06039J | | | 9 | | | | GD06733 | D.. | 2 | | 150, 152-199 |
| 909 | 20 | | PA | | 10-0 | 23-32-11 | D02233 | | | 4 | | | | SM00002 | | S | | 050-099 |
| 909 | 20 | | PA | | 3-0 | 23-32-21 | D06039J | | | 10 | | | | GD06733 | D.. | 2 | | 150, 152-199 |
| 910 | 20 | | PA | | 3-0 | 23-32-21 | D06039J | | | 11 | | | | GD06733 | D.. | 2 | | 150, 152-199 |
| 911 | 20 | | PA | | 3-0 | 23-32-21 | D06039J | | | 12 | | | | GD06733 | D.. | 2 | | 150, 152-199 |
| 912 | 20 | | PQ | AQ | 10-0 | 23-32-21 | D06039J | | | 13 | | | | D04625J | 1 | | | 150, 152-199 |
| 912Z | | | | AQ | 0-0 | 23-32-21 | D06039J | | | 14 | | | | D04625J | 2 | | | 150, 152-199 |
| 913 | 20 | | PA | | 3-0 | 23-32-21 | D06039J | | | 15 | | | | GD06733 | D.. | 2 | | 150, 152-199 |
| 914 | 20 | | PA | | 3-0 | 23-32-21 | D06039J | | | 16 | | | | GD06733 | D.. | 2 | | 150, 152-199 |
| 915 | 20 | | PA | | 3-0 | 23-32-21 | D06039J | | | | | | FN | GD06733 | S.. | 2 | | 150, 152-199 |
| 916 | 20 | | PA | | 10-0 | 23-32-21 | D06039J | | | 5 | | | | D04340P | 8 | | | 150, 152-199 |
| 917 | 20 | | PQ | AT | 10-0 | 23-32-21 | D06039J | | | 6 | | | | D04340P | 10 | | | 150, 152-199 |
| 917Z | | | | AT | 0-0 | 23-32-21 | D06039J | | | | | | FN | D04340P | DED | | | 150, 152-199 |
| 918 | 20 | | PA | | 10-0 | 23-32-21 | SP00003 | | | | 9 | | | D04571J | 26 | | | 150, 152-199 |
| 919B | 22 | | PR | AV | 10-0 | 23-32-21 | D06165J | | | 3 | | | | D04393J | 20 | | | 150, 152-199 |
| 919R | 22 | | PR | AV | 0-0 | 23-32-21 | D06165J | | | 2 | | | | D04393J | 19 | | | 150, 152-199 |
| 919Z | | | | AV | 0-0 | 23-32-21 | D06165J | | | 1 | | | | D04393J | 18 | | | 150, 152-199 |
| 920B | 22 | | PR | AW | 10-0 | 23-32-21 | D06165J | | | 5 | | | | D04393J | 22 | | | 150, 152-199 |
| 920R | 22 | | PR | AW | 0-0 | 23-32-21 | D06165J | | | 4 | | | | D04393J | 21 | | | 150, 152-199 |
| 920Z | | | | AW | 0-0 | 23-32-21 | D06165J | | | 6 | | | | D04393J | 23 | | | 150, 152-199 |
| 921 | 20 | | PA | | 10-0 | 23-32-21 | D06165J | | | 7 | | | | D04393J | 24 | | | 150, 152-199 |
| 922 | 20 | | PA | | 10-0 | 23-32-21 | D06165J | | | 8 | | | | D04393J | 25 | | | 150, 152-199 |
| 923 | 24 | | PK | | 64-0 | 23-32-13 | D02233 | | | 6 | | | | SM00003 | | S | | 050-099 |
| 923 | 20 | | PA | | 10-0 | 23-32-21 | D06165J | | | 9 | | | | D04393J | 26 | | | 150, 152-199 |
| 924 | 24 | | PK | | 64-0 | 23-32-13 | D02233 | | | 7 | | | | SM00004 | | S | | 050-099 |
| 924B | 22 | | PR | AX | 10-0 | 23-32-21 | D05109J | | | 8 | | | | D04571J | 24 | | | 150, 152-199 |
| 924R | 22 | | PR | AX | 0-0 | 23-32-21 | D05109J | | | 7 | | | | D04571J | 23 | | | 150, 152-199 |
| 924Z | | | | AX | 0-0 | 23-32-21 | D05109J | | | | | | FA | D04571J | | | FB | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W1410

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1417 | 286T1417 | | | VIDEO SYSTEM-FROM P37 TO FWD,MID,AFT PROJECTOR AND VIDEO CENTER (continued) | | | | | | | | | | | |
| 925 | 24 | | PK | | 64-0 | 23-32-13 | D02233 | | | | SM00005 | | S | | 050-099 |
| 925B | 22 | | PR | AY | 10-0 | 23-32-21 | D05109J | | | | D04571J | 28 | | | 150, 152-199 |
| 925R | 22 | | PR | AY | 0-0 | 23-32-21 | D05109J | | | | D04571J | 27 | | | 150, 152-199 |
| 925Z | | | | AY | 0-0 | 23-32-21 | D05109J | | | FA | D04571J | | | FB | 150, 152-199 |
| 926 | 20 | | PA | | 64-0 | 23-32-13 | D02233 | | | | SM00006 | | S | | 050-099 |
| 927 | 20 | | PA | | 64-0 | 23-32-13 | D02233 | | | | SM00007 | | S | | 050-099 |
| 928 | 20 | | PA | | 64-0 | 23-32-13 | D02233 | | | | SM00008 | | S | | 050-099 |
| FRA | | | | | 0-0 | 23-32-21 | D04571J | | | | D04571J | | | FA | 050-099 |
| FRA | | | | | 0-0 | 23-32-21 | D05109J | | | FA | D05109J | 11 | | | 150, 152-199 |
| FRB | | | | | 0-0 | 23-32-21 | D06039J | | 26 | | D06039J | | | FB | 050-099 |
| FRB | | | | | 0-0 | 23-32-21 | D04571J | | | FB | D04571J | 22 | | | 150, 152-199 |
| FRC | | | | | 0-0 | 23-32-21 | D06039J | | | FC | D06039J | 26 | | | 150-199 |
| FRC | | | | | 0-0 | 23-32-21 | D06099J | | | FC | D06099J | 26 | | | 275-299 |
| FRD | | | | | 0-0 | 23-32-21 | D04571J | | | FD | D04571J | 25 | | | 150-199, 275-299 |
| FRN | | | | | 0-0 | 23-32-21 | D06039J | | | FN | D06039J | 7 | | | 150, 152-199 |
| W1419 | 286T1419 | | | VIDEO SYSTEM-COAX CABLE ANTENNA | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-32-13 | D06041J | | = C1 | | D05801P | | = C1 | | 050-099, 150-199 |
| 01CO | | | | A | 0-0 | 23-32-13 | D05597J | | = C1 | | D05801P | | = C1 | | 275-299 |
| 01CX | | | | BR A | 108-0 | 23-32-13 | D06041J | | = A1 | | D05801P | | = A1 | | 050-099 |
| 01CX | | | | BR A | 129-0 | 23-32-13 | D06041J | | = A1 | | D05801P | | = A1 | | 150-199 |
| 01CX | | | | BR A | 145-0 | 23-32-13 | D05597J | | = A1 | | D05801P | | = A1 | | 275 |
| 01CX | | | | BR A | 144-0 | 23-32-13 | D05597J | | = A1 | | D05801P | | = A1 | | 276-299 |



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|--------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1423 | 286T1423 | | | CTR ZONE SEAT ELECTRONICS BOX TO AFT COLUMN TIMER DECODER | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-34-19 | D01875 | =C1 | | | | D00631 | =CF | | | ALL | |
| 01CX | | BX | A | 82-0 | 23-34-19 | D01875 | =A1 | | | | D00631 | F | | | 050-099 | |
| 01CX | | BX | A | 71-11 | 23-34-19 | D01875 | =A1 | | | | D00631 | F | | | 150-199 | |
| 01CX | | BX | A | 69-4 | 23-34-19 | D01875 | =A1 | | | | D00631 | F | | | 275-299 | |
| 201B | 16 | PB | IA | 82-0 | 23-34-19 | D01865 | | 5 | FL | | D00631 | B | FM | | 050-099 | |
| 201B | 16 | PB | IA | 72-4 | 23-34-19 | D01865 | | 5 | FL | | D00631 | B | FM | | 150-199 | |
| 201B | 16 | PB | IA | 69-9 | 23-34-19 | D01865 | | 5 | FL | | D00631 | B | FM | | 275-278 | |
| 201B | 16 | PB | IA | 69-3 | 23-34-19 | D01865 | | 5 | FL | | D00631 | B | FM | | 280-299 | |
| 201R | 16 | PB | IA | 0-0 | 23-34-19 | D01865 | | 4 | FL | | D00631 | A | FM | | ALL | |
| 301B | 24 | PM | MA | 81-0 | 23-34-19 | D01865 | | 2 | | | D00631 | D | | | 050-099 | |
| 301B | 24 | PM | MA | 72-4 | 23-34-19 | D01865 | | 2 | | | D00631 | D | | | 150-199 | |
| 301B | 24 | PM | MA | 69-9 | 23-34-19 | D01865 | | 2 | | | D00631 | D | | | 275-278 | |
| 301B | 24 | PM | MA | 69-3 | 23-34-19 | D01865 | | 2 | | | D00631 | D | | | 280-299 | |
| 301R | 24 | PM | MA | 0-0 | 23-34-19 | D01865 | | 1 | | | D00631 | E | | | ALL | |
| 301Y | 24 | PM | MA | 0-0 | 23-34-19 | D01865 | | 3 | | | D00631 | C | | | ALL | |
| W1427 | 286T1427 | | | COAX CABLE-LEFT ANTENNA VIDEO LO BAND | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-32-13 | D01243 | =C1 | | | | D01245 | =C1 | | | ALL | |
| 01CX | | 66 | A | 6-0 | 23-32-13 | D01243 | =A1 | | | | D01245 | =A1 | | | ALL | |
| W1429 | 286T1429 | | | COAX CABLE-LEFT ANTENNA VIDEO HI BAND | | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-32-13 | D01235 | =C1 | | | | D01237 | =C1 | | | ALL | |
| 01CX | | 66 | A | 10-0 | 23-32-13 | D01235 | =A1 | | | | D01237 | =A1 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1420

Page 1 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|---------|-------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1431 | 286T1431 | | | | COAX CABLE-RIGHT ANTENNA VIDEO LO BAND | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-32-13 | D01247 | = C1 | | D01249 | = C1 | | | | ALL |
| 01CX | | 66 | | A | 6-0 | 23-32-13 | D01247 | = A1 | | D01249 | = A1 | | | | ALL |
| W1433 | 286T1433 | | | | COAX CABLE-RIGHT ANTENNA VIDEO HI BAND | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-32-13 | D01239 | = C1 | | D01241 | = C1 | | | | ALL |
| 01CX | | 66 | | A | 12-0 | 23-32-13 | D01239 | = A1 | | D01241 | = A1 | | | | ALL |
| W1435 | 286T1435 | | | | P2 TO E8 SHELF-EICAS UPPER DISPLAY UNIT | | | | | | | | | | |
| 001 | 22 | | PA | | 9-0 | 31-41-11 | D00205 | | 6 | D05111J | | 1 | | | ALL |
| 002 | 20 | | PA | | 1-0 | 31-41-11 | D00205 | | 7 | GD0001 | A.. | 2 | | | ALL |
| 003 | 20 | | PA | | 1-0 | 31-41-11 | D00205 | | 17 | GD0001 | S.. | 2 | | | ALL |
| 004 | 24 | | PK | | 20-0 | 31-41-12 | D00205 | | 22 | D05055P | | 1 | | | ALL |
| 005 | 24 | | PK | | 20-0 | 31-41-12 | D00205 | | 23 | D05055P | | 2 | | | ALL |
| 007 | 24 | | PK | | 14-0 | 31-41-16 | D05055P | | 7 | D05111J | | 14 | | | ALL |
| 008 | 24 | | PK | | 14-0 | 31-41-16 | D05055P | | 8 | D05111J | | 15 | | | ALL |
| 009 | 22 | | PA | | 14-0 | 31-41-17 | D05111J | | 16 | D05055P | | 9 | | | ALL |
| 010 | 22 | | PA | | 14-0 | 31-41-17 | D05111J | | 17 | D05055P | | 10 | | | ALL |
| 012 | 22 | | PA | | 14-0 | SPARE | D05055P | | 35 | D05111J | | 20 | | | ALL |
| 013 | 22 | | PA | | 14-0 | SPARE | D05055P | | 36 | D05111J | | 21 | | | ALL |
| 014 | 22 | | PA | | 14-0 | SPARE | D05055P | | 37 | D05111J | | 22 | | | ALL |
| 201B | 24 | | PW | IA | 14-0 | 31-41-12 | D05111J | | 3 | D05055P | | 5 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 31-41-12 | D05111J | | 2 | D05055P | | 4 | | | ALL |
| 201Z | | | | IA | 0-0 | 31-41-12 | D05111J | | 4 | D05055P | | 6 | | | ALL |
| 202B | 24 | | PL | IB | 9-0 | 31-41-14 | D00205 | | 29 | D05111J | | 6 | | | ALL |
| 202R | 24 | | PL | IB | 0-0 | 31-41-14 | D00205 | | 28 | D05111J | | 5 | | | ALL |
| 203B | 24 | | PL | IC | 9-0 | 31-41-14 | D00205 | | 13 | D05111J | | 8 | | | ALL |
| 203R | 24 | | PL | IC | 0-0 | 31-41-14 | D00205 | | 12 | D05111J | | 7 | | | ALL |
| 204B | 24 | | PL | ID | 9-0 | 31-41-14 | D00205 | | 27 | D05111J | | 10 | | | ALL |
| 204R | 24 | | PL | ID | 0-0 | 31-41-14 | D00205 | | 26 | D05111J | | 9 | | | ALL |
| 205W | 24 | | BV | IE | 20-0 | 31-41-21 | D00205 | | 50 | D05055P | | 12 | | | ALL |
| 205WN | 24 | | BV | IE | 0-0 | 31-41-21 | D00205 | | 49 | D05055P | | 11 | | | ALL |
| 205Z | | | | IE | 0-0 | 31-41-21 | GD0001 | S.. | 2 | D05055P | | 13 | | | ALL |
| 206W | 24 | | BV | IF | 20-0 | 31-41-21 | D00205 | | 52 | D05055P | | 15 | | | ALL |
| 206WN | 24 | | BV | IF | 0-0 | 31-41-21 | D00205 | | 51 | D05055P | | 14 | | | ALL |
| 206Z | | | | IF | 0-0 | 31-41-21 | GD0001 | S.. | 2 | D05055P | | 16 | | | ALL |
| 207W | 24 | | BV | IG | 20-0 | 31-41-21 | D00205 | | 54 | D05055P | | 18 | | | ALL |
| 207WN | 24 | | BV | IG | 0-0 | 31-41-21 | D00205 | | 53 | D05055P | | 17 | | | ALL |
| 207Z | | | | IG | 0-0 | 31-41-21 | GD0001 | S.. | 2 | D05055P | | 19 | | | ALL |
| 208W | 24 | | BV | IH | 20-0 | 31-41-21 | D00205 | | 64 | D05055P | | 21 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1430
Page 1
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1435 | 286T1435 | | | P2 TO E8 SHELF-EICAS UPPER DISPLAY UNIT (continued) | | | | | | | | | | | | |
| 208WN | 24 | BV | IH | 0-0 | 31-41-21 | D00205 | 63 | | | | D05055P | 20 | | | ALL | |
| 208Z | | | IH | 0-0 | 31-41-21 | GDX0001 | S.. | 2 | | | D05055P | 22 | | | ALL | |
| 209W | 24 | BV | II | 20-0 | 31-41-22 | D00205 | 56 | | | | D05055P | 24 | | | ALL | |
| 209WN | 24 | BV | II | 0-0 | 31-41-22 | D00205 | 55 | | | | D05055P | 23 | | | ALL | |
| 209Z | | | II | 0-0 | 31-41-22 | GDX0002 | S.. | 2 | | | D05055P | 25 | | | ALL | |
| 210W | 24 | BV | IJ | 20-0 | 31-41-22 | D00205 | 58 | | | | D05055P | 27 | | | ALL | |
| 210WN | 24 | BV | IJ | 0-0 | 31-41-22 | D00205 | 57 | | | | D05055P | 26 | | | ALL | |
| 210Z | | | IJ | 0-0 | 31-41-22 | GDX0002 | S.. | 2 | | | D05055P | 28 | | | ALL | |
| 211W | 24 | BV | IK | 20-0 | 31-41-22 | D00205 | 61 | | | | D05055P | 30 | | | ALL | |
| 211WN | 24 | BV | IK | 0-0 | 31-41-22 | D00205 | 62 | | | | D05055P | 29 | | | ALL | |
| 211Z | | | IK | 0-0 | 31-41-22 | GDX0002 | S.. | 2 | | | D05055P | 31 | | | ALL | |
| 212W | 24 | BV | IL | 20-0 | 31-41-22 | D00205 | 60 | | | | D05055P | 33 | | | ALL | |
| 212WN | 24 | BV | IL | 0-0 | 31-41-22 | D00205 | 59 | | | | D05055P | 32 | | | ALL | |
| 212Z | | | IL | 0-0 | 31-41-22 | GDX0002 | S.. | 2 | | | D05055P | 34 | | | ALL | |
| 301B | 24 | PM | MA | 9-0 | 31-41-14 | D00205 | 31 | | | | D05111J | 12 | | | ALL | |
| 301R | 24 | PM | MA | 0-0 | 31-41-14 | D00205 | 30 | | | | D05111J | 11 | | | ALL | |
| 301Y | 24 | PM | MA | 0-0 | 31-41-14 | D00205 | 32 | | | | D05111J | 13 | | | ALL | |
| W1437 | 286T1437 | | | P2 TO E8 SHELF-EICAS LOWER DISPLAY UNIT | | | | | | | | | | | | |
| 001 | 22 | PA | | 8-0 | 31-41-11 | D00207 | 6 | | | | D05113J | 1 | | | ALL | |
| 002 | 20 | PA | | 1-0 | 31-41-11 | D00207 | 7 | | | | GDX0001 | A.. | 2 | | ALL | |
| 003 | 20 | PA | | 1-0 | 31-41-11 | D00207 | 17 | | | | GDX0001 | S.. | 2 | | ALL | |
| 004 | 24 | PK | | 21-0 | 31-41-12 | D00207 | 22 | | | | D05057P | 1 | | | ALL | |
| 005 | 24 | PK | | 21-0 | 31-41-12 | D00207 | 23 | | | | D05057P | 2 | | | ALL | |
| 012 | 22 | PA | | 16-0 | SPARE | D05113J | 20 | | | | D05057P | 35 | | | ALL | |
| 013 | 22 | PA | | 16-0 | SPARE | D05113J | 21 | | | | D05057P | 36 | | | ALL | |
| 014 | 22 | PA | | 16-0 | SPARE | D05113J | 22 | | | | D05057P | 37 | | | ALL | |
| 201B | 24 | PW | IA | 16-0 | 31-41-12 | D05113J | 3 | | | | D05057P | 5 | | | ALL | |
| 201R | 24 | PW | IA | 0-0 | 31-41-12 | D05113J | 2 | | | | D05057P | 4 | | | ALL | |
| 201Z | | | IA | 0-0 | 31-41-12 | D05113J | 4 | | | | D05057P | 6 | | | ALL | |
| 202B | 24 | PL | IB | 8-0 | 31-41-14 | D05113J | 6 | | | | D00207 | 29 | | | ALL | |
| 202R | 24 | PL | IB | 0-0 | 31-41-14 | D05113J | 5 | | | | D00207 | 28 | | | ALL | |
| 203B | 24 | PL | IC | 8-0 | 31-41-14 | D05113J | 8 | | | | D00207 | 27 | | | ALL | |
| 203R | 24 | PL | IC | 0-0 | 31-41-14 | D05113J | 7 | | | | D00207 | 26 | | | ALL | |
| 204B | 24 | PL | ID | 8-0 | 31-41-14 | D05113J | 10 | | | | D00207 | 13 | | | ALL | |
| 204R | 24 | PL | ID | 0-0 | 31-41-14 | D05113J | 9 | | | | D00207 | 12 | | | ALL | |
| 205W | 24 | BV | IE | 21-0 | 31-41-23 | D00207 | 50 | | | | D05057P | 12 | | | ALL | |
| 205WN | 24 | BV | IE | 0-0 | 31-41-23 | D00207 | 49 | | | | D05057P | 11 | | | ALL | |
| 205Z | | | IE | 0-0 | 31-41-23 | GDX0001 | S.. | 2 | | | D05057P | 13 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1430

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1437 | 286T1437 | | | P2 TO E8 SHELF-EICAS LOWER DISPLAY UNIT (continued) | | | | | | | | | | | | |
| 206W | 24 | BV | IF | 21-0 | 31-41-23 | D00207 | | 52 | | | | D05057P | 15 | | ALL | |
| 206WN | 24 | BV | IF | 0-0 | 31-41-23 | D00207 | | 51 | | | | D05057P | 14 | | ALL | |
| 206Z | | | IF | 0-0 | 31-41-23 | GDX0001 | | S.. | 2 | | | D05057P | 16 | | ALL | |
| 207W | 24 | BV | IG | 21-0 | 31-41-23 | D00207 | | 54 | | | | D05057P | 18 | | ALL | |
| 207WN | 24 | BV | IG | 0-0 | 31-41-23 | D00207 | | 53 | | | | D05057P | 17 | | ALL | |
| 207Z | | | IG | 0-0 | 31-41-23 | GDX0001 | | S.. | 2 | | | D05057P | 19 | | ALL | |
| 208W | 24 | BV | IH | 21-0 | 31-41-23 | D00207 | | 64 | | | | D05057P | 21 | | ALL | |
| 208WN | 24 | BV | IH | 0-0 | 31-41-23 | D00207 | | 63 | | | | D05057P | 20 | | ALL | |
| 208Z | | | IH | 0-0 | 31-41-23 | GDX0001 | | S.. | 2 | | | D05057P | 22 | | ALL | |
| 209W | 24 | BV | II | 21-0 | 31-41-24 | D00207 | | 56 | | | | D05057P | 24 | | ALL | |
| 209WN | 24 | BV | II | 0-0 | 31-41-24 | D00207 | | 55 | | | | D05057P | 23 | | ALL | |
| 209Z | | | II | 0-0 | 31-41-24 | GDX0002 | | S.. | 2 | | | D05057P | 25 | | ALL | |
| 210W | 24 | BV | IJ | 21-0 | 31-41-24 | D00207 | | 58 | | | | D05057P | 27 | | ALL | |
| 210WN | 24 | BV | IJ | 0-0 | 31-41-24 | D00207 | | 57 | | | | D05057P | 26 | | ALL | |
| 210Z | | | IJ | 0-0 | 31-41-24 | GDX0002 | | S.. | 2 | | | D05057P | 28 | | ALL | |
| 211W | 24 | BV | IK | 21-0 | 31-41-24 | D00207 | | 61 | | | | D05057P | 30 | | ALL | |
| 211WN | 24 | BV | IK | 0-0 | 31-41-24 | D00207 | | 62 | | | | D05057P | 29 | | ALL | |
| 211Z | | | IK | 0-0 | 31-41-24 | GDX0002 | | S.. | 2 | | | D05057P | 31 | | ALL | |
| 212W | 24 | BV | IL | 21-0 | 31-41-24 | D00207 | | 60 | | | | D05057P | 33 | | ALL | |
| 212WN | 24 | BV | IL | 0-0 | 31-41-24 | D00207 | | 59 | | | | D05057P | 32 | | ALL | |
| 212Z | | | IL | 0-0 | 31-41-24 | GDX0002 | | S.. | 2 | | | D05057P | 34 | | ALL | |
| 301B | 24 | PM | MA | 8-0 | 31-41-14 | D05113J | | 12 | | | | D00207 | 31 | | ALL | |
| 301R | 24 | PM | MA | 0-0 | 31-41-14 | D05113J | | 11 | | | | D00207 | 30 | | ALL | |
| 301Y | 24 | PM | MA | 0-0 | 31-41-14 | D05113J | | 13 | | | | D00207 | 32 | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W1430
Page 3 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|-------|------|------|--------|---------|-------------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W1443 | 286T1443 | | | LEFT-AFT ZONE PSUD & SEAT ELEX BOX TO AFT COLUMN TIMER DECODER | | | | | | | | | | | |
| 001 | 24 | | PK | | 1-0 | 23-34-18 | D05531J | | 1 | | | SM00002 | | 9 | ALL |
| 002 | 16 | | PA | | 1-0 | 23-34-18 | D05531J | | 2 | FL | | SM00001 | | 9 | ALL |
| 003 | 16 | | PA | | 9-0 | 23-34-18 | D05531J | | 3 | FL | | GD01566 | A.. | E | 050-099 |
| 003 | 16 | | PA | | 4-0 | 23-34-18 | D05531J | | 3 | FL | | GD00721 | A.. | E | 150-199, 275-299 |
| 004 | 24 | | PK | | 3-0 | 23-34-18 | D05533J | | 4 | | | D05531J | | 4 | ALL |
| 005 | 24 | | PK | | 1-0 | 23-34-18 | D05533J | | 1 | | | SM00002 | | 9 | ALL |
| 006 | 16 | | PA | | 9-0 | 23-34-18 | D05533J | | 3 | FL | | GD01566 | A.. | E | 050-099 |
| 006 | 16 | | PA | | 4-0 | 23-34-18 | D05533J | | 3 | FL | | GD00721 | A.. | E | 150-199, 275-299 |
| 007 | 16 | | PA | | 1-0 | 23-34-18 | D05533J | | 2 | FL | | SM00001 | | 9 | ALL |
| 008 | 12 | | PA | | 113-0 | 23-34-18 | SP00057 | | | | S | SM00001 | | 9 | 050-099 |
| 008 | 12 | | PA | | 119-0 | 23-34-18 | SP00057 | | | | | SM00001 | | 9 | 150-199, 275-299 |
| 01C0 | | | | A | 0-0 | 23-34-18 | D01877 | | | =C1 | | D01885 | =CF | | ALL |
| 01CX | | | | BX A | 81-0 | 23-34-18 | D01877 | | | =A1 | | D01885 | F | | 050-099 |
| 01CX | | | | BX A | 78-9 | 23-34-18 | D01877 | | | =A1 | | D01885 | F | | 150-199, 275-299 |
| 201B | 16 | | PB | IA | 79-0 | 23-34-18 | D01859 | | 5 | FL | | D01885 | B | FM | 050-099 |
| 201B | 16 | | PB | IA | 78-0 | 23-34-18 | D01859 | | 5 | FL | | D01885 | B | FM | 150-199, 275-299 |
| 201R | 16 | | PB | IA | 0-0 | 23-34-18 | D01859 | | 4 | FL | | D01885 | A | FM | ALL |
| 301B | 24 | | PM | MA | 79-0 | 23-34-18 | D01859 | | 2 | | | D01885 | D | | 050-099 |
| 301B | 24 | | PM | MA | 78-0 | 23-34-18 | D01859 | | 2 | | | D01885 | D | | 150-199, 275-299 |
| 301R | 24 | | PM | MA | 0-0 | 23-34-18 | D01859 | | 1 | | | D01885 | E | | ALL |
| 301Y | 24 | | PM | MA | 0-0 | 23-34-18 | D01859 | | 3 | | | D01885 | C | | ALL |
| 302B | 24 | | PM | MB | 84-0 | 23-34-18 | D01857 | | 2 | | | D05533J | 5 | | 050-099 |
| 302B | 24 | | PM | MB | 91-0 | 23-34-18 | D01857 | | 2 | | | D05533J | 5 | | 150-199, 275-278 |
| 302B | 24 | | PM | MB | 101-0 | 23-34-18 | D01857 | | 2 | | | D05533J | 5 | | 280-299 |
| 302R | 24 | | PM | MB | 0-0 | 23-34-18 | D01857 | | 1 | | | D05531J | 5 | | ALL |
| 302Y | 24 | | PM | MB | 0-0 | 23-34-18 | D01857 | | 3 | | | SM00002 | | 9 | ALL |
| W1445 | 286T1445 | | | RIGHT AFT ZONE PSUD & SEAT ELEX. BOX TO AFT COLUMN TIMER DECODER | | | | | | | | | | | |
| 001 | 24 | | PK | | 1-0 | 23-34-18 | D05449J | | 1 | | | SM00002 | | 9 | ALL |
| 002 | 16 | | PA | | 1-0 | 23-34-18 | D05449J | | 2 | FL | | SM00001 | | 9 | ALL |
| 003 | 16 | | PA | | 10-0 | 23-34-18 | D05449J | | 3 | FL | | GD01476 | A.. | E | 050-099 |
| 003 | 16 | | PA | | 4-0 | 23-34-18 | D05449J | | 3 | FL | | GD00715 | A.. | E | 150-199, 275-299 |
| 004 | 24 | | PK | | 1-0 | 23-34-18 | D05451J | | 4 | | | D05449J | 4 | | 050-099 |
| 004 | 24 | | PK | | 3-0 | 23-34-18 | D05451J | | 4 | | | D05449J | 4 | | 150-199, 275-299 |
| 005 | 24 | | PK | | 1-0 | 23-34-18 | D05451J | | 1 | | | SM00002 | | 9 | ALL |
| 006 | 16 | | PA | | 10-0 | 23-34-18 | D05451J | | 3 | FL | | GD01476 | A.. | E | 050-099 |
| 006 | 16 | | PA | | 4-0 | 23-34-18 | D05451J | | 3 | FL | | GD00715 | A.. | E | 150-199, 275-299 |
| 007 | 16 | | PA | | 1-0 | 23-34-18 | D05451J | | 2 | FL | | SM00001 | | 9 | ALL |
| 008 | 12 | | PA | | 99-0 | 23-34-18 | SP00053 | | | | S | SM00001 | | 9 | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1440

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1445 | 286T1445 | | | RIGHT AFT ZONE PSUD & SEAT ELEX. BOX TO AFT COLUMN TIMER DECODER (continued) | | | | | | | | | | | |
| 008 | 12 | | PA | | 107-0 | 23-34-18 | SP00053 | | 9 | | SM00001 | | 9 | | 150-199, 275-299 |
| 01CO | | | | A | 0-0 | 23-34-18 | D01873 | = C1 | | | D01883 | = CF | | | ALL |
| 01CX | | | | BX | 75-0 | 23-34-18 | D01873 | = A1 | | | D01883 | F | | | 050-099 |
| 01CX | | | | BX | 68-0 | 23-34-18 | D01873 | = A1 | | | D01883 | F | | | 150-199, 275-299 |
| 201B | 16 | | PB | IA | 72-0 | 23-34-18 | D01861 | 5 | FL | | D01883 | B | FM | | 050-099 |
| 201B | 16 | | PB | IA | 68-6 | 23-34-18 | D01861 | 5 | FL | | D01883 | B | FM | | 150-199, 275-299 |
| 201R | 16 | | PB | IA | 0-0 | 23-34-18 | D01861 | 4 | FL | | D01883 | A | FM | | ALL |
| 301B | 24 | | PM | MA | 72-0 | 23-34-18 | D01861 | 2 | | | D01883 | D | | | 050-099 |
| 301B | 24 | | PM | MA | 68-6 | 23-34-18 | D01861 | 2 | | | D01883 | D | | | 150-199, 275-299 |
| 301R | 24 | | PM | MA | 0-0 | 23-34-18 | D01861 | 1 | | | D01883 | E | | | ALL |
| 301Y | 24 | | PM | MA | 0-0 | 23-34-18 | D01861 | 3 | | | D01883 | C | | | ALL |
| 302B | 24 | | PM | MB | 75-0 | 23-34-18 | D01855 | 2 | | | D05451J | 5 | | | 050-099 |
| 302B | 24 | | PM | MB | 82-3 | 23-34-18 | D01855 | 2 | | | D05451J | 5 | | | 150-199, 275-299 |
| 302R | 24 | | PM | MB | 0-0 | 23-34-18 | D01855 | 1 | | | D05449J | 5 | | | ALL |
| 302Y | 24 | | PM | MB | 0-0 | 23-34-18 | D01855 | 3 | | | SM00002 | | 9 | | ALL |
| W1447 | 286T1447 | | | PURSER STATION/VIDEO CONTROL/CREW REST JUMPER BUNDLE | | | | | | | | | | | |
| 001 | 20 | | PA | | 16-0 | 23-32-11 | D06035P | 21 | | | D06047P | 21 | | | 050-099, 150-199 |
| 002 | 16 | | PA | | 16-0 | 23-32-11 | D06035P | 23 | | | D06047P | 23 | | | 050-099, 150-199 |
| 003 | 20 | | PA | | 16-0 | 23-32-11 | D06035P | 3 | | | D06047P | 3 | | | 050-099, 150-199 |
| 004 | 20 | | PQ | AD | 16-0 | 23-32-11 | D06037P | 1 | | | D06045P | 1 | | | 050-099, 150-199 |
| 004Z | | | | AD | 0-0 | 23-32-11 | D06037P | 24 | | | D06045P | 18 | | | 050-099, 150-199 |
| 005 | 20 | | PA | | 16-0 | 23-32-11 | D06037P | 2 | | | D06045P | 2 | | | 050-099, 150-199 |
| 006 | 20 | | PA | | 16-0 | 23-32-11 | D06037P | 3 | | | D06045P | 3 | | | 050-099, 150-199 |
| 007 | 20 | | PA | | 16-0 | 23-32-11 | D06037P | 4 | | | D06045P | 4 | | | 050-099, 150-199 |
| 008 | 24 | | PK | | 16-0 | 23-32-12 | D06035P | 4 | | | D06047P | 4 | | | 050-099, 150-199 |
| 009 | 24 | | PK | | 16-0 | 23-32-12 | D06035P | 5 | | | D06047P | 5 | | | 050-099, 150-199 |
| 010 | 24 | | PK | | 16-0 | 23-32-12 | D06035P | 8 | | | D06047P | 8 | | | 050-099, 150-199 |
| 011 | 24 | | PK | | 16-0 | 23-32-13 | D06037P | 5 | | | D06045P | 5 | | | 050-099, 150-199 |
| 012 | 24 | | PK | | 16-0 | 23-32-13 | D06037P | 6 | | | D06045P | 6 | | | 050-099, 150-199 |
| 013 | 24 | | PK | | 16-0 | 23-32-13 | D06037P | 7 | | | D06045P | 7 | | | 050-099, 150-199 |
| 014 | 20 | | PA | | 16-0 | 23-32-13 | D06037P | 8 | | | D06045P | 8 | | | 050-099, 150-199 |
| 015 | 24 | | PK | | 16-0 | 23-32-13 | D06037P | 9 | | | D06045P | 9 | | | 050-099, 150-199 |
| 016 | 24 | | PK | | 16-0 | 23-32-13 | D06037P | 10 | | | D06045P | 10 | | | 050-099, 150-199 |
| 017 | 24 | | PK | | 16-0 | 23-32-13 | D06037P | 11 | | | D06045P | 11 | | | 050-099, 150-199 |
| 018 | 20 | | PA | | 16-0 | 23-32-13 | D06037P | 12 | | | D06045P | 12 | | | 050-099, 150-199 |
| 019 | 24 | | PK | | 16-0 | 23-32-13 | D06037P | 13 | | | D06045P | 13 | | | 050-099, 150-199 |
| 01CO | | | | A | 0-0 | 23-32-13 | D06041P | = C1 | | | D06049P | = C1 | | | 050-099, 150-199 |
| 01CX | | | | BR | 16-0 | 23-32-13 | D06041P | = A1 | | | D06049P | = A1 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1440

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|-------|------|--------|-------|------|---------|--------|-----|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W1447 | 286T1447 | | | PURSER STATION/VIDEO CONTROL/CREW REST JUMPER BUNDLE (continued) | | | | | | | | | | | | | | |
| 020 | 24 | | PK | | 16-0 | 23-32-13 | D06037P | | 14 | | | | D06045P | | 14 | | | 050-099, 150-199 |
| 021 | 24 | | PK | | 16-0 | 23-32-13 | D06037P | | 16 | | | | D06045P | | 16 | | | 050-099, 150-199 |
| 022 | 20 | | PA | | 16-0 | 23-32-13 | D06037P | | 17 | | | | D06045P | | 17 | | | 050-099, 150-199 |
| 02CO | | | | B | 0-0 | 23-32-13 | D06037P | = C19 | | | | | D06045P | = C19 | | | | 050-099, 150-199 |
| 02CX | | 5X | | B | 16-0 | 23-32-13 | D06037P | | 19 | | | | D06045P | | 19 | | | 050-099, 150-199 |
| 03CO | | | | C | 0-0 | 23-32-13 | D06037P | = C23 | | | | | D06045P | = C23 | | | | 050-099, 150-199 |
| 03CX | | 5X | | C | 16-0 | 23-32-13 | D06037P | | 23 | | | | D06045P | | 23 | | | 050-099, 150-199 |
| 04CO | | | | D | 0-0 | 23-32-13 | D06037P | = C27 | | | | | D06045P | = C27 | | | | 050-099, 150-199 |
| 04CX | | 5X | | D | 16-0 | 23-32-13 | D06037P | | 27 | | | | D06045P | | 27 | | | 050-099, 150-199 |
| 056 | 24 | | PK | | 16-0 | 23-31-11 | D06031P | | 1 | | | | D06043P | | 1 | | | 150-199 |
| 057 | 24 | | PK | | 16-0 | 23-31-11 | D06031P | | 2 | | | | D06043P | | 2 | | | 150-199 |
| 058 | 24 | | PK | | 16-0 | 23-31-13 | D06031P | | 6 | | | | D06043P | | 6 | | | 050-099, 150-199 |
| 059 | 24 | | PK | | 16-0 | 23-31-12 | D06031P | | 7 | | | | D06043P | | 7 | | | 050-099, 150-199 |
| 05CO | | | | E | 0-0 | 23-32-21 | D06037P | = C15 | | | | | D06045P | = C15 | | | | 050-099, 150-199 |
| 05CX | | 5X | | E | 16-0 | 23-32-21 | D06037P | | 15 | | | | D06045P | | 15 | | | 050-099, 150-199 |
| 060 | 24 | | PK | | 16-0 | 23-31-13 | D06031P | | 8 | | | | D06043P | | 8 | | | 050-099, 150-199 |
| 061 | 24 | | PK | | 16-0 | 23-31-13 | D06031P | | 9 | | | | D06043P | | 9 | | | 050-099, 150-199 |
| 062 | 24 | | PK | | 16-0 | 23-31-13 | D06031P | | 10 | | | | D06043P | | 10 | | | 050-099, 150-199 |
| 063 | 24 | | PK | | 16-0 | 23-31-13 | D06031P | | 11 | | | | D06043P | | 11 | | | 050, 162-166 |
| 063 | 24 | | PK | | 16-0 | 23-31-14 | D06031P | | 11 | | | | D06043P | | 11 | | | 051-099, 150-157, 167-199 |
| 064 | 24 | | PK | | 16-0 | 23-31-13 | D06031P | | 12 | | | | D06043P | | 12 | | | 050, 162-166 |
| 064 | 24 | | PK | | 16-0 | 23-31-14 | D06031P | | 12 | | | | D06043P | | 12 | | | 051-099, 150-157, 167-199 |
| 067 | 22 | | PA | | 16-0 | 23-31-12 | D06031P | | 24 | | | | D06043P | | 24 | | | 050-099, 150-199 |
| 068 | 22 | | PA | | 16-0 | 23-31-12 | D06031P | | 23 | | | | D06043P | | 23 | | | 050-099, 150-199 |
| 069 | 22 | | PA | | 16-0 | 23-31-12 | D06031P | | 21 | | | | D06043P | | 21 | | | 050-099, 150-199 |
| 070 | 24 | | PK | | 16-0 | 23-31-12 | D06031P | | 27 | | | | D06043P | | 27 | | | 050-099, 150-199 |
| 075 | 20 | | PA | | 6-0 | 23-42-11 | D06111J | | 1 | | | | GD00763 | | D.. | 2 | | 050-099 |
| 075 | 20 | | PA | | 8-0 | 23-42-11 | GD00763 | | D.. | 2 | | | D06111J | | 1 | | | 162-199 |
| 076 | 22 | | PA | | 23-0 | 23-42-11 | D06111J | | 2 | | | | D06031P | | 41 | | | 050-099 |
| 076 | 22 | | PA | | 22-0 | 23-42-11 | D06031P | | 41 | | | | D06111J | | 2 | | | 162-199 |
| 077 | 22 | | PA | | 23-0 | 23-42-11 | D06111J | | 5 | | | | D06031P | | 32 | | | 050-099 |
| 077 | 22 | | PA | | 22-0 | 23-42-11 | D06031P | | 32 | | | | D06111J | | 5 | | | 162-199 |
| 078 | 20 | | PA | | 6-0 | 23-42-11 | D06111J | | 6 | | | | GD00763 | | D.. | 2 | | 050-099 |
| 078 | 20 | | PA | | 8-0 | 23-42-11 | D06111J | | 6 | | | | GD00763 | | D.. | 2 | | 162-199 |
| 101 | 24 | | PV | EA | 16-0 | 23-32-12 | D06035P | | 6 | | | | D06047P | | 6 | | | 050-099, 150-199 |
| 101Z | | | | EA | 0-0 | 23-32-12 | D06035P | | 7 | | | | D06047P | | 7 | | | 050-099, 150-199 |
| 102 | 24 | | PV | EB | 16-0 | 23-32-12 | D06035P | | 9 | | | | D06047P | | 9 | | | 050-099, 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1440

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1447 | 286T1447 | | | PURSER STATION/VIDEO CONTROL/CREW REST JUMPER BUNDLE (continued) | | | | | | | | | | | | |
| 102Z | | | | EB | 0-0 | 23-32-12 | D06035P | | | | FA | D06047P | | | FB | 050-099, 150-199 |
| 103 | 24 | | PV | EC | 16-0 | 23-32-12 | D06035P | | 10 | | | D06047P | 10 | | | 050-099, 150-199 |
| 103Z | | | | EC | 0-0 | 23-32-12 | D06035P | | | | FA | D06047P | | | FB | 050-099, 150-199 |
| 104 | 24 | | PV | ED | 16-0 | 23-32-12 | D06035P | | 11 | | | D06047P | 11 | | | 050-099, 150-199 |
| 104Z | | | | ED | 0-0 | 23-32-12 | D06035P | | | | FA | D06047P | | | FB | 050-099, 150-199 |
| 105 | 24 | | PV | EE | 16-0 | 23-32-12 | D06035P | | 12 | | | D06047P | 12 | | | 050-099, 150-199 |
| 105Z | | | | EE | 0-0 | 23-32-12 | D06035P | | | | FA | D06047P | | | FB | 050-099, 150-199 |
| 106 | 24 | | PV | EF | 16-0 | 23-32-12 | D06035P | | 13 | | | D06047P | 13 | | | 050-099, 150-199 |
| 106Z | | | | EF | 0-0 | 23-32-12 | D06035P | | | | FA | D06047P | | | FB | 050-099, 150-199 |
| 107 | 24 | | PV | EG | 16-0 | 23-32-12 | D06035P | | 14 | | | D06047P | 14 | | | 050-099, 150-199 |
| 107Z | | | | EG | 0-0 | 23-32-12 | D06035P | | | | FA | D06047P | | | FB | 050-099, 150-199 |
| 108 | 22 | | PA | | 16-0 | 23-32-12 | D06035P | | 18 | | | D06047P | 18 | | | 050-099, 150-199 |
| 109 | 22 | | PA | | 16-0 | 23-32-12 | D06035P | | 16 | | | D06047P | 16 | | | 050-099, 150-199 |
| 110 | 22 | | PA | | 16-0 | 23-32-12 | D06035P | | 17 | | | D06047P | 17 | | | 050-099, 150-199 |
| 111 | 24 | | PV | EK | 16-0 | 23-34-14 | D06043P | | 28 | | | D06031P | 28 | | | 050-099, 150-199 |
| 111Z | | | | EK | 0-0 | 23-34-14 | D06043P | | 29 | | | D06031P | 29 | | | 050-099, 150-199 |
| 112 | 24 | | PV | EL | 16-0 | 23-34-14 | D06043P | | 30 | | | D06031P | 30 | | | 050-099, 150-199 |
| 112Z | | | | EL | 0-0 | 23-34-14 | D06043P | | 31 | | | D06031P | 31 | | | 050-099, 150-199 |
| 201B | 24 | | PW | IA | 16-0 | 23-32-21 | D06039P | | 22 | | | D06047P | 22 | | | 050-099, 150-199 |
| 201R | 24 | | PW | IA | 0-0 | 23-32-21 | D06039P | | 20 | | | D06047P | 20 | | | 050-099, 150-199 |
| 201Z | | | | IA | 0-0 | 23-32-21 | D06039P | | | | FC | D06047P | | | FD | 050-099, 150-199 |
| 202B | 24 | | PW | IB | 16-0 | 23-32-21 | D06039P | | 25 | | | D06047P | 25 | | | 050-099, 150-199 |
| 202R | 24 | | PW | IB | 0-0 | 23-32-21 | D06039P | | 24 | | | D06047P | 24 | | | 050-099, 150-199 |
| 202Z | | | | IB | 0-0 | 23-32-21 | D06039P | | | | FC | D06047P | | | FD | 050-099, 150-199 |
| 203B | 24 | | PW | IC | 16-0 | 23-32-21 | D06039P | | 34 | | | D06047P | 34 | | | 050-099, 150-199 |
| 203R | 24 | | PW | IC | 0-0 | 23-32-21 | D06039P | | 33 | | | D06047P | 33 | | | 050-099, 150-199 |
| 203Z | | | | IC | 0-0 | 23-32-21 | D06039P | | | | FC | D06047P | | | FD | 050-099, 150-199 |
| 205B | 24 | | PW | IE | 16-0 | 23-31-11 | D06031P | | 4 | | | D06043P | 4 | | | 150-199 |
| 205R | 24 | | PW | IE | 0-0 | 23-31-11 | D06031P | | 3 | | | D06043P | 3 | | | 150-199 |
| 205Z | | | | IE | 0-0 | 23-31-11 | D06031P | | 5 | | | D06043P | 5 | | | 150-199 |
| 206B | 20 | | PB | IF | 16-0 | 23-22-12 | D06031P | | 20 | | | D06043P | 20 | | | 050-099, 150-199 |
| 206R | 20 | | PB | IF | 0-0 | 23-22-12 | D06031P | | 19 | | | D06043P | 19 | | | 050-099, 150-199 |
| 207 | 20 | | UA | | 1-6 | 23-22-12 | GD06901 | | S.. | E | | D06043P | | | FE | 050-099, 153-199 |
| 207 | 20 | | UA | | 1-6 | 23-22-12 | GD02204 | | S.. | E | | D06043P | | | FE | 150-152 |
| 207B | 24 | | PW | IG | 16-0 | 23-22-12 | D06031P | | 17 | | | D06043P | 17 | | | 050-099, 150-199 |
| 207R | 24 | | PW | IG | 0-0 | 23-22-12 | D06031P | | 16 | | | D06043P | 16 | | | 050-099, 150-199 |
| 207Z | | | | IG | 0-0 | 23-22-12 | D06031P | | 18 | | | D06043P | | | FE | 050-099, 150-199 |
| 208 | 20 | | UA | | 1-6 | 23-22-12 | GD06901 | | S.. | E | | D06043P | | | FF | 050-099, 153-199 |
| 208 | 20 | | UA | | 1-6 | 23-22-12 | GD02204 | | S.. | E | | D06043P | | | FF | 150-152 |

WIRE LIST

D280T132

91-21-11

Section W1440

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|-------|-------------|------|------|--------|----|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type | Splice | | |
| W1447 | 286T1447 | | | PURSER STATION/VIDEO CONTROL/CREW REST JUMPER BUNDLE (continued) | | | | | | | | | | | | | | |
| 208B | 24 | PW | IH | | 16-0 | 23-22-12 | D06031P | | 14 | | | | D06043P | | 14 | | | 050-099, 150-199 |
| 208R | 24 | PW | IH | | 0-0 | 23-22-12 | D06031P | | 13 | | | | D06043P | | 13 | | | 050-099, 150-199 |
| 208Z | | | IH | | 0-0 | 23-22-12 | D06031P | | 15 | | | | D06043P | | | FF | | 050-099, 150-199 |
| 216B | 24 | PW | IP | | 16-0 | 23-31-12 | D06031P | | 25 | | | | D06043P | | 25 | | | 050-099, 150-199 |
| 216R | 24 | PW | IP | | 0-0 | 23-31-12 | D06031P | | 26 | | | | D06043P | | 26 | | | 050-099, 150-199 |
| 216Z | | | IP | | 0-0 | 23-31-12 | D06031P | | 22 | | | | D06043P | | 22 | | | 050-099, 150-199 |
| 301B | 24 | PX | MA | | 16-0 | 23-32-21 | D06039P | | 27 | | | | D06047P | | 27 | | | 050-099, 150-199 |
| 301R | 24 | PX | MA | | 0-0 | 23-32-21 | D06039P | | 28 | | | | D06047P | | 28 | | | 050-099, 150-199 |
| 301Y | 24 | PX | MA | | 0-0 | 23-32-21 | D06039P | | 29 | | | | D06047P | | 29 | | | 050-099, 150-199 |
| 301Z | | | MA | | 0-0 | 23-32-21 | D06039P | | | | FC | | D06047P | | | | FD | 050-099, 150-199 |
| 302B | 24 | PX | MB | | 16-0 | 23-32-21 | D06039P | | 30 | | | | D06047P | | 30 | | | 050-099, 150-199 |
| 302R | 24 | PX | MB | | 0-0 | 23-32-21 | D06039P | | 31 | | | | D06047P | | 31 | | | 050-099, 150-199 |
| 302Y | 24 | PX | MB | | 0-0 | 23-32-21 | D06039P | | 32 | | | | D06047P | | 32 | | | 050-099, 150-199 |
| 302Z | | | MB | | 0-0 | 23-32-21 | D06039P | | | | FC | | D06047P | | | | FD | 050-099, 150-199 |
| 401B | 20 | PD | QA | | 16-0 | 23-32-13 | D06037P | | 21 | | | | D06047P | | 37 | | | 050-099, 150-199 |
| 401G | 20 | PD | QA | | 0-0 | 23-32-13 | D06037P | | 18 | | | | D06047P | | 35 | | | 050-099, 150-199 |
| 401R | 20 | PD | QA | | 0-0 | 23-32-13 | D06037P | | 22 | | | | D06047P | | 38 | | | 050-099, 150-199 |
| 401Y | 20 | PD | QA | | 0-0 | 23-32-13 | D06037P | | 20 | | | | D06047P | | 36 | | | 050-099, 150-199 |
| 402B | 24 | PY | QB | | 23-0 | 23-42-11 | D06111J | | 37 | | | | D06031P | | 37 | | | 050-099 |
| 402B | 24 | PY | QB | | 22-0 | 23-42-11 | D06031P | | 37 | | | | D06111J | | 37 | | | 162-199 |
| 402G | 24 | PY | QB | | 0-0 | 23-42-11 | D06111J | | 39 | | | | D06031P | | 39 | | | 050-099 |
| 402G | 24 | PY | QB | | 0-0 | 23-42-11 | D06031P | | 39 | | | | D06111J | | 39 | | | 162-199 |
| 402R | 24 | PY | QB | | 0-0 | 23-42-11 | D06111J | | 36 | | | | D06031P | | 36 | | | 050-099 |
| 402R | 24 | PY | QB | | 0-0 | 23-42-11 | D06031P | | 36 | | | | D06111J | | 36 | | | 162-199 |
| 402Y | 24 | PY | QB | | 0-0 | 23-42-11 | D06111J | | 38 | | | | D06031P | | 38 | | | 050-099 |
| 402Y | 24 | PY | QB | | 0-0 | 23-42-11 | D06031P | | 38 | | | | D06111J | | 38 | | | 162-199 |
| 402Z | | | QB | | 0-0 | 23-42-11 | D06111J | | 40 | | | | D06031P | | 40 | | | 050-099 |
| 402Z | | | QB | | 0-0 | 23-42-11 | D06031P | | 40 | | | | D06111J | | 40 | | | 162-199 |
| 900 | 20 | PA | | | 10-0 | 23-32-21 | D06047P | | 1 | | | | D06039P | | 1 | | | 150, 152-199 |
| 901 | 20 | PA | | | 10-0 | 23-32-21 | D06047P | | 2 | | | | D06039P | | 2 | | | 150, 152-199 |
| 902 | 20 | PA | | | 10-0 | 23-32-21 | D06047P | | 19 | | | | D06039P | | 3 | | | 150, 152-199 |
| 903 | 20 | PA | | | 10-0 | 23-32-21 | D06047P | | 39 | | | | D06039P | | 4 | | | 150, 152-199 |
| 904 | 20 | PA | | | 10-0 | 23-32-21 | D06039P | | 5 | | | | D09091P | | 1 | | | 150, 152-199 |
| 905 | 20 | PQ | AH | | 10-0 | 23-32-21 | D06039P | | 6 | | | | D09091P | | 2 | | | 150, 152-199 |
| 905Z | | | AH | | 0-0 | 23-32-21 | D06039P | | 7 | | | | D09091P | | 3 | | | 150, 152-199 |
| 906 | 20 | PA | | | 10-0 | 23-32-21 | D06039P | | 8 | | | | D09091P | | 4 | | | 150, 152-199 |
| 907 | 20 | PA | | | 10-0 | 23-32-21 | D06039P | | 9 | | | | D09091P | | 5 | | | 150, 152-199 |
| 908 | 20 | PA | | | 10-0 | 23-32-21 | D06039P | | 10 | | | | D09091P | | 6 | | | 150, 152-199 |
| 909 | 20 | PA | | | 10-0 | 23-32-21 | D06039P | | 11 | | | | D09091P | | 7 | | | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W1440

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|-------|--------|---------|------|-------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1447 | 286T1447 | | | PURSER STATION/VIDEO CONTROL/CREW REST JUMPER BUNDLE (continued) | | | | | | | | | | | |
| 910 | 20 | | PA | | 10-0 | 23-32-21 | D06039P | | | | D09091P | | | | 150, 152-199 |
| 911 | 20 | | PQ | AJ | 10-0 | 23-32-21 | D06039P | | | | D09091P | | | | 150, 152-199 |
| 911Z | | | | AJ | 0-0 | 23-32-21 | D06039P | | | | D09091P | | | | 150, 152-199 |
| 912 | 20 | | PA | | 10-0 | 23-32-21 | D06039P | | | | D09091P | | | | 150, 152-199 |
| 913 | 20 | | PA | | 10-0 | 23-32-21 | D06039P | | | | D09091P | | | | 150, 152-199 |
| FRA | | | | | 0-0 | 23-32-12 | D06035P | | | FA | D06035P | | | | 050-099, 150-199 |
| FRB | | | | | 0-0 | 23-32-12 | D06047P | | | FB | D06047P | | | | 050-099, 150-199 |
| FRC | | | | | 0-0 | 23-32-21 | D06039P | 26 | | | D06039P | | | FC | 050-099, 150-199 |
| FRD | | | | | 0-0 | 23-32-21 | D06047P | 26 | | | D06047P | | | FD | 050-099, 150-199 |
| FRE | | | | | 0-0 | 23-22-12 | D06043P | | | FE | D06043P | 18 | | | 050-099, 150-199 |
| FRF | | | | | 0-0 | 23-22-12 | D06043P | | | FF | D06043P | 15 | | | 050-099, 150-199 |
| W1449 | 286T1449 | | | PURSER STATION/VIDEO CONTROL/CREW REST JUMPER BUNDLE | | | | | | | | | | | |
| 001 | 22 | | PA | | 17-0 | 33-21-21 | D13442P | | 1 | | D13444P | | 1 | | 050-099, 150-199 |
| 002 | 22 | | PA | | 17-0 | 33-21-21 | D13442P | | 2 | | D13444P | | 2 | | 050-099, 150-199 |
| 003 | 22 | | PA | | 17-0 | 33-21-21 | D13442P | | 3 | | D13444P | | 3 | | 050-099, 150-199 |
| 004 | 20 | | PA | | 17-0 | 33-21-21 | D13442P | | 4 | | D13444P | | 4 | | 050-099, 150-199 |
| 005 | 22 | | PA | | 17-0 | 33-21-21 | D13442P | | 5 | | D13444P | | 5 | | 050-099, 150-199 |
| 006 | 24 | | PK | | 17-0 | 33-21-31 | D13442P | | 6 | | D13444P | | 6 | | 050-099, 150-199 |
| 008 | 24 | | PK | | 17-0 | 33-21-31 | D13442P | | 8 | | D13444P | | 8 | | 050-099, 150-199 |
| 009 | 24 | | PK | | 17-0 | 33-21-31 | D13442P | | 9 | | D13444P | | 9 | | 050-099, 150-199 |
| 011 | 20 | | PA | | 17-0 | 33-21-31 | D13442P | | 11 | | D13444P | | 11 | | 050-099, 150-199 |
| 012 | 24 | | PK | | 17-0 | 33-21-31 | D13442P | | 12 | | D13444P | | 12 | | 050-099, 155-199 |
| 012 | 20 | | PA | | 17-0 | 33-21-31 | D13442P | | 12 | | D13444P | | 12 | | 150-154 |
| 013 | 22 | | PA | | 17-0 | 33-22-32 | D13442P | | 13 | | D13444P | | 13 | | 050-099, 150-199 |
| 014 | 20 | | PA | | 17-0 | 33-22-32 | D13442P | | 14 | | D13444P | | 14 | | 050-099, 150-199 |
| 015 | 20 | | PA | | 17-0 | 33-22-32 | D13442P | | 15 | | D13444P | | 15 | | 050-099, 150-199 |
| 016 | 22 | | PA | | 17-0 | 33-24-12 | D13442P | | 16 | | D13444P | | 16 | | 050-099, 150-199 |
| 017 | 20 | | PA | | 17-0 | 33-24-12 | D13442P | | 17 | | D13444P | | 17 | | 050-099, 150-199 |
| 018 | 22 | | PA | | 17-0 | 33-24-12 | D13442P | | 18 | | D13444P | | 18 | | 050-099, 150-199 |
| 01CO | | | | A | 0-0 | 23-34-15 | D06109J | | = C15 | | D06107P | | = C15 | | 050-099, 162-199 |
| 01CX | | | 5X | A | 21-0 | 23-34-15 | D06109J | | 15 | | D06107P | | 15 | | 050-099, 162-199 |
| 021 | 20 | | PA | | 17-0 | 33-21-11 | D13444P | | 21 | | D08688P | | 1 | | 050-099 |
| 021 | 20 | | PA | | 17-0 | 33-21-11 | D08688P | | 1 | | D13444P | | 21 | | 150-199 |
| 022 | 24 | | PK | | 17-0 | 33-21-11 | D13444P | | 22 | | D08688P | | 2 | | 050-099 |
| 022 | 24 | | PK | | 17-0 | 33-21-11 | D08688P | | 2 | | D13444P | | 22 | | 150-199 |
| 023 | 24 | | PK | | 17-0 | 33-21-11 | D13444P | | 23 | | D08688P | | 3 | | 050-099 |
| 023 | 24 | | PK | | 17-0 | 33-21-11 | D08688P | | 3 | | D13444P | | 23 | | 150-199 |
| 024 | 20 | | PA | | 17-0 | 33-21-11 | D13444P | | 24 | | D08688P | | 4 | | 050-099 |

WIRE LIST

D280T132

91-21-11

Section W1440

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1449 | 286T1449 | | | PURSER STATION/VIDEO CONTROL/CREW REST JUMPER BUNDLE (continued) | | | | | | | | | | | | |
| 024 | 20 | | PA | 17-0 | 33-21-11 | D08688P | | 4 | | | D13444P | 24 | | | 150-199 | |
| 025 | 24 | | PK | 17-0 | 33-21-11 | D13444P | | 25 | | | D08688P | 5 | | | 050-099 | |
| 025 | 24 | | PK | 17-0 | 33-21-11 | D08688P | | 5 | | | D13444P | 25 | | | 150-199 | |
| 026 | 24 | | PK | 17-0 | 33-21-11 | D13444P | | 26 | | | D08688P | 6 | | | 050-099 | |
| 026 | 24 | | PK | 17-0 | 33-21-11 | D08688P | | 6 | | | D13444P | 26 | | | 150-199 | |
| 027 | 20 | | PA | 17-0 | 33-21-11 | D13444P | | 27 | | | D08688P | 7 | | | 050-099 | |
| 027 | 20 | | PA | 17-0 | 33-21-11 | D08688P | | 7 | | | D13444P | 27 | | | 150-199 | |
| 028 | 24 | | PK | 17-0 | 33-21-11 | D13444P | | 28 | | | D08688P | 8 | | | 050-099 | |
| 028 | 20 | | PA | 17-0 | 33-21-11 | D08688P | | 8 | | | D13444P | 28 | | | 150-199 | |
| 029 | 24 | | PK | 17-0 | 33-21-12 | D08688P | | 9 | | | D13444P | 29 | | | 050-099, 150-199 | |
| 030 | 20 | | PA | 17-0 | 33-21-12 | D08688P | | 10 | | | D13444P | 30 | | | 050-099, 150-199 | |
| 031 | 24 | | PK | 17-0 | 33-21-12 | D08688P | | 11 | | | D13444P | 31 | | | 050-099, 150-199 | |
| 032 | 24 | | PK | 17-0 | 33-21-12 | D08688P | | 12 | | | D13444P | 32 | | | 050-099 | |
| 032 | 20 | | PA | 17-0 | 33-21-12 | D08688P | | 12 | | | D13444P | 32 | | | 150-199 | |
| 033 | 24 | | PK | 17-0 | 33-21-12 | D08688P | | 13 | | | D13444P | 33 | | | 050-099, 150-199 | |
| 034 | 24 | | PK | 17-0 | 33-21-12 | D08688P | | 14 | | | D13444P | 34 | | | 050-099, 150-199 | |
| 035 | 24 | | PK | 17-0 | 33-21-12 | D08688P | | 15 | | | D13444P | 35 | | | 050-099, 150-199 | |
| 036 | 24 | | PK | 17-0 | 33-21-12 | D08688P | | 16 | | | D13444P | 36 | | | 050-099, 150-199 | |
| 039 | 22 | | PA | 17-0 | 33-22-42 | D08688P | | 22 | | | D13444P | 39 | | | 050-099, 150-199 | |
| 040 | 22 | | PA | 17-0 | 33-22-42 | D08688P | | 24 | | | D13444P | 40 | | | 050-099, 150-199 | |
| 042 | 22 | | PA | 17-0 | 23-42-11 | D06033P | | 1 | | | D13444P | 42 | | | 050-099, 150-199 | |
| 043 | 22 | | PA | 17-0 | 33-22-41 | D08688P | | 17 | | | D13444P | 43 | | | 050-099, 150-199 | |
| 044 | 22 | | PA | 17-0 | 33-22-41 | D08688P | | 18 | | | D13444P | 44 | | | 050-099, 150-199 | |
| 045 | 22 | | PA | 17-0 | 33-22-41 | D08688P | | 19 | | | D13444P | 45 | | | 050-099, 150-199 | |
| 046 | 22 | | PA | 17-0 | 33-22-41 | D08688P | | 20 | | | D13444P | 46 | | | 050-099, 150-199 | |
| 054 | 24 | | PK | 4-0 | 33-21-12 | D08688P | | 21 | | | D13442P | 7 | | | 050-099, 150-199 | |
| 067 | 20 | | PA | 17-0 | 33-26-21 | D08688P | | 30 | | | D13444P | 47 | | | 050-099, 150-157, 167-199 | |
| 067 | 20 | | PA | 17-0 | 23-31-13 | D08688P | | 30 | | | D13444P | 47 | | | 162-166 | |
| 068 | 20 | | PA | 17-0 | 33-26-21 | D08688P | | 31 | | | D13444P | 48 | | | 050-099, 150-157, 167-199 | |
| 068 | 20 | | PA | 17-0 | 23-31-13 | D08688P | | 31 | | | D13444P | 48 | | | 162-166 | |
| 069 | 20 | | PA | 17-0 | 33-26-21 | D08688P | | 32 | | | D13444P | 49 | | | 050-099, 150-157, 167-199 | |
| 069 | 20 | | PA | 17-0 | 23-31-13 | D08688P | | 32 | | | D13444P | 49 | | | 162-166 | |
| 070 | 20 | | PA | 17-0 | 33-26-21 | D08688P | | 33 | | | D13444P | 50 | | | 050-099, 150-157, 167-199 | |
| 070 | 20 | | PA | 17-0 | 23-31-13 | D08688P | | 33 | | | D13444P | 50 | | | 162-166 | |
| 072 | 16 | | PA | 22-0 | 23-34-15 | D06125J | | 2 | FM | | D06105P | 2 | FL | | 050-099, 162-199 | |

WIRE LIST

D280T132

91-21-11

Section W1440

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1449 | 286T1449 | | | PURSER STATION/VIDEO CONTROL/CREW REST JUMPER BUNDLE (continued) | | | | | | | | | | | |
| 073 | 16 | | PA | | 22-0 | 23-34-15 | D06125J | 3 | FM | | D06105P | 3 | FL | | 050-099, 162-199 |
| 078 | 22 | | PA | | 22-0 | 33-22-33 | D08706P | 6 | | | D06109J | 9 | | | 050-099, 162-199 |
| 083 | 20 | | PA | | 6-0 | 33-22-33 | D06109J | 10 | | | GD00763 | A.. | 2 | | 050-099 |
| 083 | 20 | | PA | | 6-0 | 33-22-33 | GD00763 | A.. | 2 | | D06109J | 10 | | | 162-199 |
| 085 | 20 | | PA | | 22-0 | 33-26-21 | D06109J | 11 | | | D08706P | 4 | | | 050-099, 162-199 |
| 086 | 22 | | PA | | 22-0 | 33-24-13 | D06125J | 8 | | | D08706P | 12 | | | 050-099 |
| 086 | 20 | | PA | | 22-0 | 33-24-13 | D06125J | 8 | | | D08706P | 12 | | | 162-199 |
| 089 | 22 | | PA | | 22-0 | 33-24-13 | D06125J | 9 | | | D08706P | 13 | | | 050-099, 162-199 |
| 090 | 20 | | PA | | 6-0 | 33-24-13 | D06125J | 10 | | | GD00763 | A.. | 2 | | 050-099, 162-199 |
| 097 | 20 | | PA | | 22-0 | 33-51-13 | D08706P | 7 | | | D06109J | 13 | | | 050-099 |
| 097 | 20 | | PA | | 22-0 | 33-51-13 | D06109J | 13 | | | D08706P | 7 | | | 162-199 |
| 100 | 20 | | PA | | 6-0 | 33-51-13 | D06109J | 14 | | | GD00763 | D.. | 2 | | 050-099, 162-199 |
| 114 | 22 | | PA | | 22-0 | 23-42-11 | D06123J | 11 | | | D06033P | 3 | | | 050-099, 162-199 |
| 118 | 20 | | PA | | 6-0 | 23-42-11 | D06123J | 12 | | | GD00763 | D.. | 2 | | 050-099, 162-199 |
| 119 | 22 | | PA | | 22-0 | 23-42-11 | D06123J | 13 | | | D06033P | 2 | | | 050-099, 162-199 |
| 123 | 20 | | PA | | 22-0 | 26-13-12 | D08706P | 5 | | | D06123J | 27 | | | 050-099, 162-199 |
| 124 | 20 | | PA | | 22-0 | SPARE | D08706P | 2 | | | D06123J | 28 | | | 050-099 |
| 125 | 20 | | PA | | 22-0 | 26-13-12 | D08706P | 3 | | | D06123J | 29 | | | 050-099, 162-199 |
| 126 | 20 | | PA | | 22-0 | 26-13-12 | D06123J | 30 | | | D08706P | 18 | | | 050-099 |
| 126 | 20 | | PA | | 22-0 | 26-13-12 | D08706P | 18 | | | D06123J | 30 | | | 162-199 |
| 129 | 22 | | PA | | 22-0 | 23-42-11 | D06109J | 17 | | | D06033P | 5 | | | 050-099, 162-199 |
| 130 | 22 | | PA | | 22-0 | 23-42-11 | D06109J | 18 | | | D06033P | 4 | | | 050-099, 162-199 |
| 140 | 20 | | PA | | 22-0 | 35-21-14 | D06125J | 6 | | | D08706P | 1 | | | 050-099 |
| 140 | 20 | | PA | | 22-0 | 35-21-14 | D08706P | 1 | | | D06125J | 6 | | | 162-199 |
| 141 | 20 | | PA | | 6-0 | 35-21-14 | D06125J | 7 | | | GD00763 | D.. | 2 | | 050-099, 162-199 |
| 142 | 20 | | PA | | 6-0 | 23-34-15 | D06109J | 16 | | | GD00763 | A.. | 2 | | 050-099, 162-199 |
| 144 | 20 | | PA | | 6-0 | 33-26-21 | D06109J | 12 | | | GD00763 | A.. | 2 | | 050-099, 162-199 |
| 146 | 20 | | PA | | 22-0 | 26-13-12 | D06123J | 25 | | | D08706P | 14 | | | 050-099 |
| 146 | 20 | | PA | | 22-0 | 26-13-12 | D08706P | 14 | | | D06123J | 25 | | | 162-199 |
| 147 | 20 | | PA | | 22-0 | 26-13-12 | D06123J | 26 | | | D08706P | 15 | | | 050-099 |
| 147 | 20 | | PA | | 22-0 | 26-13-12 | D08706P | 15 | | | D06123J | 26 | | | 162-199 |
| 163 | 20 | | PA | | 6-0 | 21-66-11 | GD00763 | D.. | 2 | | D06123J | 14 | | | 050-099, 162-199 |
| 164 | 20 | | PA | | 6-0 | 21-66-11 | GD00763 | D.. | 2 | | D06123J | 17 | | | 050-099, 162-199 |
| 165 | 22 | | PA | | 22-0 | 21-66-11 | D08706P | 8 | | | D06123J | 16 | | | 050-099, 162-199 |
| 166 | 22 | | PA | | 22-0 | 21-66-11 | D08706P | 9 | | | D06123J | 18 | | | 050-099, 162-199 |
| 169 | 20 | | PA | | 6-0 | 21-66-11 | GD00763 | S.. | 2 | | D06123J | 21 | | | 050-099, 162-199 |
| 170 | 22 | | PA | | 22-0 | 21-66-11 | D06123J | 15 | | | D08706P | 16 | | | 050-099, 162-199 |
| 171 | 22 | | PA | | 22-0 | 21-66-11 | D06123J | 19 | | | D08706P | 17 | | | 050-099, 162-199 |
| 174 | 22 | | PA | | 22-0 | 21-66-11 | D08706P | 28 | | | D06123J | 3 | | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W1440

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|---------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1449 | 286T1449 | | | PURSER STATION/VIDEO CONTROL/CREW REST JUMPER BUNDLE (continued) | | | | | | | | | | | |
| 179 | 20 | | PA | 6-0 | 21-66-11 | GD00763 | D.. | 2 | | D06123J | | 5 | | | 050-099, 162-199 |
| 180 | 20 | | PA | 13-2 | 33-26-21 | D13444P | | 7 | | GD01022 | A.. | E | | | 150, 153-155 |
| 180 | 20 | | PA | 11-0 | 33-26-21 | D13444P | | 7 | | GD01022 | A.. | E | | | 151-152 |
| 180 | 20 | | PA | 9-0 | 33-26-21 | D13444P | | 7 | | GD01022 | A.. | E | | | 156-157, 167-199 |
| 180 | 20 | | PA | 13-2 | 23-31-13 | D13444P | | 7 | | GD01022 | A.. | E | | | 162-165 |
| 180 | 20 | | PA | 9-0 | 23-31-13 | D13444P | | 7 | | GD01022 | A.. | E | | | 166 |
| 203B | 20 | | PB | IC | 22-0 | 23-34-15 | D06109J | | 2 | | D06107P | | 2 | | 050-099, 162-199 |
| 203R | 20 | | PB | IC | 0-0 | 23-34-15 | D06109J | | 1 | | D06107P | | 1 | | 050-099, 162-199 |
| 205B | 22 | | PB | IE | 22-0 | 21-66-11 | D08706P | | 10 | | D06123J | | 22 | | 050-099, 162-199 |
| 205R | 22 | | PB | IE | 0-0 | 21-66-11 | D08706P | | 11 | | D06123J | | 23 | | 050-099, 162-199 |
| 303B | 24 | | PM | MC | 22-0 | 23-34-15 | D06109J | | 5 | | D06107P | | 5 | | 050-099, 162-199 |
| 303R | 24 | | PM | MC | 0-0 | 23-34-15 | D06109J | | 4 | | D06107P | | 4 | | 050-099, 162-199 |
| 303Y | 24 | | PM | MC | 0-0 | 23-34-15 | D06109J | | 3 | | D06107P | | 3 | | 050-099, 162-199 |
| 304B | 24 | | PM | MD | 22-0 | 23-34-15 | D06125J | | 4 | | D06105P | | 4 | | 050-099, 162-199 |
| 304R | 24 | | PM | MD | 0-0 | 23-34-15 | D06125J | | 5 | | D06105P | | 5 | | 050-099, 162-199 |
| 304Y | 24 | | PM | MD | 0-0 | 23-34-15 | D06125J | | 1 | | D06105P | | 1 | | 050-099, 162-199 |
| 305B | 22 | | PC | ME | 22-0 | 21-66-11 | D08706P | | 24 | | D06109J | | 8 | | 050-099, 162-199 |
| 305R | 22 | | PC | ME | 0-0 | 21-66-11 | D08706P | | 25 | | D06109J | | 7 | | 050-099, 162-199 |
| 305Y | 22 | | PC | ME | 0-0 | 21-66-11 | D08706P | | 26 | | D06109J | | 6 | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W1440

Page 9 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------|-------------------------------------|---------|-------|------|------|--------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1463 | 286T1463 | | | | PSUD LOOP-TO-LOOP 48 INCHES | | | | | | | | | | | |
| 201B | 16 | PB | IA | 5-0 | 23-34 | D01569 | 3 | FM | | D01571 | 3 | FM | | 050-099, 162-199, 275-276 | | |
| 201R | 16 | PB | IA | 0-0 | 23-34 | D01569 | 2 | FM | | D01571 | 2 | FM | | 050-099, 162-199, 275-276 | | |
| 301B | 24 | PM | MA | 5-0 | 23-34 | D01569 | 4 | | | D01571 | 4 | | | 050-099, 162-199, 275-276 | | |
| 301R | 24 | PM | MA | 0-0 | 23-34 | D01569 | 5 | | | D01571 | 5 | | | 050-099, 162-199, 275-276 | | |
| 301Y | 24 | PM | MA | 0-0 | 23-34 | D01569 | 1 | | | D01571 | 1 | | | 050-099, 162-199, 275-276 | | |
| W1465 | 286T1465 | | | | PSUD LOOP-TO-LOOP 53 INCHES | | | | | | | | | | | |
| 201B | 16 | PB | IA | 6-0 | 23-34 | D01573 | 3 | FM | | D01575 | 3 | FM | | ALL | | |
| 201R | 16 | PB | IA | 0-0 | 23-34 | D01573 | 2 | FM | | D01575 | 2 | FM | | ALL | | |
| 301B | 24 | PM | MA | 6-0 | 23-34 | D01573 | 4 | | | D01575 | 4 | | | ALL | | |
| 301R | 24 | PM | MA | 0-0 | 23-34 | D01573 | 5 | | | D01575 | 5 | | | ALL | | |
| 301Y | 24 | PM | MA | 0-0 | 23-34 | D01573 | 1 | | | D01575 | 1 | | | ALL | | |
| W1467 | 286T1467 | | | | PSUD LOOP-TO-LOOP 60 INCHES | | | | | | | | | | | |
| 201B | 16 | PB | IA | 6-0 | 23-34 | D01577 | 3 | FM | | D01579 | 3 | FM | | ALL | | |
| 201R | 16 | PB | IA | 0-0 | 23-34 | D01577 | 2 | FM | | D01579 | 2 | FM | | ALL | | |
| 301B | 24 | PM | MA | 6-0 | 23-34 | D01577 | 4 | | | D01579 | 4 | | | ALL | | |
| 301R | 24 | PM | MA | 0-0 | 23-34 | D01577 | 5 | | | D01579 | 5 | | | ALL | | |
| 301Y | 24 | PM | MA | 0-0 | 23-34 | D01577 | 1 | | | D01579 | 1 | | | ALL | | |
| W1469 | 286T1469 | | | | PSUD LOOP-TO-LOOP 138 INCHES | | | | | | | | | | | |
| 201B | 16 | PB | IA | 13-0 | 23-34 | D01581 | 3 | FM | | D01583 | 3 | FM | | 050-099, 162-199, 275-299 | | |
| 201R | 16 | PB | IA | 0-0 | 23-34 | D01581 | 2 | FM | | D01583 | 2 | FM | | 050-099, 162-199, 275-299 | | |
| 301B | 24 | PM | MA | 13-0 | 23-34 | D01581 | 4 | | | D01583 | 4 | | | 050-099, 162-199, 275-299 | | |
| 301R | 24 | PM | MA | 0-0 | 23-34 | D01581 | 5 | | | D01583 | 5 | | | 050-099, 162-199, 275-299 | | |
| 301Y | 24 | PM | MA | 0-0 | 23-34 | D01581 | 1 | | | D01583 | 1 | | | 050-099, 162-199, 275-299 | | |

WIRE LIST
D280T132

91-21-11
Section W1460
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|------|------|---|---------|-------|------|------|--------|-------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1471 | 286T1471 | | | | PSUD LOOP-TO-LOOP 200 INCHES | | | | | | | | | | | |
| 201B | 16 | PB | IA | 18-0 | 23-34 | D01585 | 3 | FM | | D01587 | 3 | FM | | | ALL | |
| 201R | 16 | PB | IA | 0-0 | 23-34 | D01585 | 2 | FM | | D01587 | 2 | FM | | | ALL | |
| 301B | 24 | PM | MA | 18-0 | 23-34 | D01585 | 4 | | | D01587 | 4 | | | | ALL | |
| 301R | 24 | PM | MA | 0-0 | 23-34 | D01585 | 5 | | | D01587 | 5 | | | | ALL | |
| 301Y | 24 | PM | MA | 0-0 | 23-34 | D01585 | 1 | | | D01587 | 1 | | | | ALL | |
| W1473 | 286T1473 | | | | PSUD LOOP-TO-LOOP 290 INCHES | | | | | | | | | | | |
| 201B | 16 | PB | IA | 26-0 | 23-34 | D01589 | 3 | FM | | D01591 | 3 | FM | | | 150-199 | |
| 201R | 16 | PB | IA | 0-0 | 23-34 | D01589 | 2 | FM | | D01591 | 2 | FM | | | 150-199 | |
| 301B | 24 | PM | MA | 26-0 | 23-34 | D01589 | 4 | | | D01591 | 4 | | | | 150-199 | |
| 301R | 24 | PM | MA | 0-0 | 23-34 | D01589 | 5 | | | D01591 | 5 | | | | 150-199 | |
| 301Y | 24 | PM | MA | 0-0 | 23-34 | D01589 | 1 | | | D01591 | 1 | | | | 150-199 | |
| W1477 | 286T1477 | | | | PSUD LOOP-TO-LOOP 84 INCHES | | | | | | | | | | | |
| 201B | 16 | PB | IA | 8-0 | 23-34 | D01597 | 3 | FM | | D01599 | 3 | FM | | | 050-099, 150-199, 277-299 | |
| 201R | 16 | PB | IA | 0-0 | 23-34 | D01597 | 2 | FM | | D01599 | 2 | FM | | | 050-099, 150-199, 277-299 | |
| 301B | 24 | PM | MA | 8-0 | 23-34 | D01597 | 4 | | | D01599 | 4 | | | | 050-099, 150-199, 277-299 | |
| 301R | 24 | PM | MA | 0-0 | 23-34 | D01597 | 5 | | | D01599 | 5 | | | | 050-099, 150-199, 277-299 | |
| 301Y | 24 | PM | MA | 0-0 | 23-34 | D01597 | 1 | | | D01599 | 1 | | | | 050-099, 150-199, 277-299 | |
| W1479 | 286T1479 | | | | COAX CABLE-MID TO AFT ZONE MULTIPLEXER | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-34-14 | D01887 | | = C1 | | D01871 | | = C1 | | | ALL | |
| 01CX | | | BX A | 47-0 | 23-34-14 | D01887 | | = A1 | | D01871 | | = A1 | | | 050-099 | |
| 01CX | | | BX A | 47-1 | 23-34-14 | D01887 | | = A1 | | D01871 | | = A1 | | | 150-199, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W1470
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|---|-------------|----|----|-------------|-------|----------|--------|------|------|--------|--------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1485 286T1485 JUMPER - SEB TO SEB - RIGHT OUTBOARD CATIA DESIGN | | | | | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-34-15 | D05287 | = | CF | | D05289 | = | CF | | 280-299 |
| 01CX | | | | BX | 36-0 | 23-34-15 | D05287 | | F | | D05289 | | F | | 280-299 |
| 201B | 20 | | | PB | 36-0 | 23-34-15 | D05287 | | B | | D05289 | | B | | 280-299 |
| 201R | 20 | | | PB | 0-0 | 23-34-15 | D05287 | | A | | D05289 | | A | | 280-299 |
| 301B | 24 | | | PM | 36-0 | 23-34-15 | D05287 | | D | | D05289 | | D | | 280-299 |
| 301R | 24 | | | PM | 0-0 | 23-34-15 | D05287 | | E | | D05289 | | E | | 280-299 |
| 301Y | 24 | | | PM | 0-0 | 23-34-15 | D05287 | | C | | D05289 | | C | | 280-299 |
| W1487 286T1487 JUMPER - SEB TO SEB - CENTER | | | | | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-34-17 | D05295 | = | CF | | D05297 | = | CF | | 150-199, 280-299 |
| 01CX | | | | BX | 33-0 | 23-34-17 | D05295 | | F | | D05297 | | F | | 150-199, 280-299 |
| 201B | 20 | | | PB | 33-0 | 23-34-17 | D05295 | | B | | D05297 | | B | | 150-199 |
| 201B | 16 | | | PB | 33-0 | 23-34-17 | D05295 | | B | FM | D05297 | | B | FM | 280-299 |
| 201R | 20 | | | PB | 0-0 | 23-34-17 | D05295 | | A | | D05297 | | A | | 150-199 |
| 201R | 16 | | | PB | 0-0 | 23-34-17 | D05295 | | A | FM | D05297 | | A | FM | 280-299 |
| 301B | 24 | | | PM | 33-0 | 23-34-17 | D05295 | | D | | D05297 | | D | | 150-199, 280-299 |
| 301R | 24 | | | PM | 0-0 | 23-34-17 | D05295 | | E | | D05297 | | E | | 150-199, 280-299 |
| 301Y | 24 | | | PM | 0-0 | 23-34-17 | D05295 | | C | | D05297 | | C | | 150-199, 280-299 |
| W1489 286T1489 JUMPER - SEB TO SEB - LEFT OUTBOARD CATIA DESIGN | | | | | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-34-16 | D05355 | = | CF | | D05359 | = | CF | | 280-299 |
| 01CX | | | | BX | 36-0 | 23-34-16 | D05355 | | F | | D05359 | | F | | 280-299 |
| 201B | 20 | | | PB | 36-0 | 23-34-16 | D05355 | | B | | D05359 | | B | | 280-299 |
| 201R | 20 | | | PB | 0-0 | 23-34-16 | D05355 | | A | | D05359 | | A | | 280-299 |
| 301B | 24 | | | PM | 36-0 | 23-34-16 | D05355 | | D | | D05359 | | D | | 280-299 |
| 301R | 24 | | | PM | 0-0 | 23-34-16 | D05355 | | E | | D05359 | | E | | 280-299 |
| 301Y | 24 | | | PM | 0-0 | 23-34-16 | D05355 | | C | | D05359 | | C | | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W1480
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|----|-----------------|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1498 | | 286T1498 | | | LEFT ESCAPE HATCH HEATER BLANKET STATION 915 | | | | | | | | | | | |
| 001 | 20 | | PA | | 3-0 | 21-45-22 | D06812P | | 1 | | SP05070 | | 9 | | 150-199, 275-299 | |
| 002 | 20 | | PA | | 3-0 | 21-45-22 | D06812P | | 2 | | SP05072 | | 9 | | 150-199, 275-299 | |
| 003 | 18 | | PA | | 4-0 | 21-45-22 | D06812P | | 3 | DL | GD05796 | | S.. | E | 150-199, 275-299 | |
| A-A | | | | | 0-0 | 21-45-22 | SP05070 | | | | B00407 | | WB | | 150-199, 275-299 | |
| A-B | | | | | 0-0 | 21-45-22 | SP05072 | | | | B00407 | | W | | 150-199, 275-299 | |
| W1499 | | 286T1499 | | | E1-2 SHELF TO P6 PNL-MCDP SHORTING PLUG | | | | | | | | | | | |
| 004 | 24 | | PK | | 30-0 | 22-41-13 | D05867J | | 4 | | D01447 | | 4 | | ALL | |
| 005 | 24 | | PK | | 30-0 | 22-41-13 | D05867J | | 5 | | D01447 | | 5 | | ALL | |
| 006 | 24 | | PK | | 30-0 | 22-41-13 | D05867J | | 6 | | D01447 | | 6 | | ALL | |
| 007 | 24 | | PK | | 30-0 | 22-41-13 | D05867J | | 7 | | D01447 | | 7 | | ALL | |
| 008 | 24 | | PK | | 30-0 | 22-41-13 | D05867J | | 8 | | D01447 | | 8 | | ALL | |
| 009 | 24 | | PK | | 30-0 | 22-41-13 | D05867J | | 9 | | D01447 | | 9 | | ALL | |
| 010 | 24 | | PK | | 30-0 | 22-41-13 | D05867J | | 10 | | D01447 | | 10 | | ALL | |
| 014 | 24 | | PK | | 30-0 | 22-41-13 | D05867J | | 14 | | D01447 | | 14 | | ALL | |
| 201B | 24 | | PW | IA | 30-0 | 22-41-13 | D01447 | | 2 | | D05867J | | 2 | | ALL | |
| 201R | 24 | | PW | IA | 0-0 | 22-41-13 | D01447 | | 1 | | D05867J | | 1 | | ALL | |
| 201Z | | | | IA | 0-0 | 22-41-13 | D01447 | | 3 | | D05867J | | 3 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1490

Page 1 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|------------------------------|-----|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1500 | 286T1500 | | | RIGHT ESCAPE HATCH HEATER BLANKET STATION 915 | | | | | | | | | | | | | |
| 001 | 20 | | PA | | 3-0 | 21-45-22 | D06816P | | | | SP05074 | | | | 9 | 150-199, 275-299 | |
| 002 | 20 | | PA | | 3-0 | 21-45-22 | D06816P | | | | SP05076 | | | | 9 | 150-199, 275-299 | |
| 003 | 18 | | PA | | 4-0 | 21-45-22 | D06816P | | | | GD05800 | | S.. | E | | 150-199, 275-299 | |
| A-A | | | | | 0-0 | 21-45-22 | SP05074 | | | | B00409 | | WB | | | 150-199, 275-299 | |
| A-B | | | | | 0-0 | 21-45-22 | SP05076 | | | | B00409 | | W | | | 150-199, 275-299 | |
| W1501 | 286T1501 | | | INTERSHELF L TO P36 | | | | | | | | | | | | | |
| 001 | 22 | | PA | | 7-0 | 22-22-11 | D04353P | | | | D04351J | | | | 11 | ALL | |
| 002 | 22 | | PA | | 7-0 | 27-41-11 | D04353P | | | | D04351J | | | | 12 | 150-154 | |
| 003 | 24 | | PK | | 10-0 | SPARE | D04353P | | | | D05371J | | | | 12 | ALL | |
| 004 | 24 | | PK | | 13-0 | SPARE | D04353P | | | | D05315P | | | | 4 | ALL | |
| 005 | 24 | | PK | | 13-0 | SPARE | D04353P | | | | D05315P | | | | 5 | ALL | |
| 006 | 22 | | PA | | 10-0 | 22-21-11 | D04353P | | | | D05371J | | | | 4 | ALL | |
| 007 | 22 | | PA | | 7-0 | 31-31-14 | D04353P | | | | D04351J | | | | 24 | ALL | |
| 009 | 22 | | PA | | 13-0 | 27-09-12 | D04353P | | | | D05315P | | | | 9 | ALL | |
| 012 | 22 | | PA | | 7-0 | 22-22-11 | D04353P | | | | D04351J | | | | 2 | ALL | |
| 013Y | 22 | | PJ | | 7-0 | 27-41-11 | D04353P | | | | D04351J | | | | 1 | ALL | |
| 018 | 22 | | PA | | 7-0 | 22-24-11 | D04353P | | | | D04351J | | | | 23 | ALL | |
| 019 | 22 | | PA | | 10-0 | SPARE | D04353P | | | | D05371J | | | | 10 | ALL | |
| 020 | 22 | | PA | | 7-0 | 27-61-11 | D04353P | | | | D04351J | | | | 19 | ALL | |
| 021 | 22 | | PA | | 13-0 | 27-09-13 | D04353P | | | | D05315P | | | | 1 | ALL | |
| 022 | 22 | | PA | | 13-0 | 27-09-13 | D04353P | | | | D05315P | | | | 2 | ALL | |
| 023Y | 22 | | PJ | | 7-0 | 27-41-11 | D04353P | | | | D04351J | | | | 16 | ALL | |
| 024 | 22 | | PA | | 7-0 | 27-41-11 | D04353P | | | | D04351J | | | | 15 | ALL | |
| 025 | 24 | | PK | | 7-0 | 31-31-15 | D04353P | | | | D04351J | | | | 12 | 050-099, 155-199, 275-299 | |
| 126 | 24 | | PV | FA | 15-0 | 73-21-17 | D04351J | | | | D05315P | | | | 12 | ALL | |
| 126Z | | | | FA | 0-0 | 73-21-17 | D04351J | | | FA | D05315P | | | | | FB | ALL |
| 127 | 24 | | PV | FB | 15-0 | 73-21-17 | D04351J | | | | D05315P | | | | 11 | ALL | |
| 127Z | | | | FB | 0-0 | 73-21-17 | D04351J | | | FA | D05315P | | | | | FB | ALL |
| 201B | 24 | | PW | IA | 10-0 | 22-21-11 | D04353P | | | | D05371J | | | | 3 | ALL | |
| 201R | 24 | | PW | IA | 0-0 | 22-21-11 | D04353P | | | | D05371J | | | | 2 | ALL | |
| 201Z | | | | IA | 0-0 | 22-21-11 | D04353P | | | | D05371J | | | | 1 | ALL | |
| 205B | 24 | | PL | IE | 7-0 | 22-12-11 | D04353P | | | | D04351J | | | | 10 | ALL | |
| 205R | 24 | | PL | IE | 0-0 | 22-12-11 | D04353P | | | | D04351J | | | | 9 | ALL | |
| 206B | 24 | | PW | IF | 7-0 | 22-22-11 | D04353P | | | | D04351J | | | | 6 | ALL | |
| 206R | 24 | | PW | IF | 0-0 | 22-22-11 | D04353P | | | | D04351J | | | | 5 | ALL | |
| 206Z | | | | IF | 0-0 | 22-22-11 | D04353P | | | | D04351J | | | | 17 | ALL | |
| 207B | 24 | | PW | IG | 7-0 | 27-11-12 | D04353P | | | | D04351J | | | | 21 | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1500

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|---|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1501 | 286T1501 | | | INTERSHELF L TO P36 (continued) | | | | | | | | | | | |
| 207R | 24 | PW | IG | 0-0 | 27-11-12 | D04353P | | 30 | | D04351J | 20 | | | ALL | |
| 207Z | | | IG | 0-0 | 27-11-12 | D04353P | | 29 | | D04351J | 22 | | | ALL | |
| 208B | 22 | PB | IH | 7-0 | 27-41-11 | D04353P | | 7 | | D04351J | 14 | | | ALL | |
| 208R | 22 | PB | IH | 0-0 | 27-41-11 | D04353P | | 6 | | D04351J | 13 | | | ALL | |
| 70L | 20 | PA | | 7-0 | 29-11-14 | D04351J | | 4 | | D04353P | 37 | | | ALL | |
| 70M | 20 | PQ | CT | 7-0 | 29-11-14 | D04351J | | 18 | | D04353P | 41 | | | ALL | |
| 70MZ | | | CT | 0-0 | 29-11-14 | D04351J | | DED | | D04353P | DED | | | ALL | |
| FRA | | | | 0-0 | 73-21-17 | D04351J | | 3 | | D04351J | | | FA | 050-099, 275-299 | |
| FRA | | | | 15-0 | 73-21-17 | D04351J | | 3 | | D04351J | | | FA | 150-199 | |
| FRB | | | | 0-0 | 73-21-17 | D05315P | | 10 | | D05315P | | | FB | 050-099, 275-299 | |
| FRB | | | | 15-0 | 73-21-17 | D05315P | | 10 | | D05315P | | | FB | 150-199 | |
| W1503 | 286T1503 | | | INTERSHELF,L,E1-2 TO SHELVES | | | | | | | | | | | |
| 001 | 24 | PK | | 12-0 | SPARE | D05205J | | 1 | | D05201J | 1 | | | ALL | |
| 002 | 24 | PK | | 12-0 | SPARE | D05205J | | 2 | | D05201J | 2 | | | ALL | |
| 003 | 24 | PK | | 12-0 | SPARE | D05205J | | 3 | | D05201J | 3 | | | ALL | |
| 004 | 24 | PK | | 12-0 | SPARE | D05205J | | 4 | | D05201J | 4 | | | ALL | |
| 005 | 24 | PK | | 12-0 | SPARE | D05205J | | 5 | | D05201J | 5 | | | ALL | |
| 006 | 24 | PK | | 6-0 | 34-46-12 | D05205J | | 6 | | D04525J | 6 | | | 050-099, 150-199, 275-278 280-299 | |
| 006 | 24 | PK | | 6-0 | SPARE | D05205J | | 6 | | D04525J | 6 | | | ALL | |
| 007 | 24 | PK | | 6-0 | SPARE | D05205J | | 7 | | D04525J | 7 | | | ALL | |
| 008 | 24 | PK | | 6-0 | 34-22-16 | D05205J | | 8 | | D04525J | 8 | | | ALL | |
| 010 | 22 | PA | | 6-0 | 34-22-16 | D05205J | | 55 | | D04525J | 24 | | | ALL | |
| 017 | 24 | PK | | 6-0 | 22-41-11 | D04525J | | 17 | | D05205J | 37 | | | ALL | |
| 044 | 22 | PA | | 6-0 | 34-46-12 | D05205J | | 44 | | D04525J | 4 | | | ALL | |
| 045 | 22 | PA | | 6-0 | SPARE | D05205J | | 45 | | D04525J | 29 | | | ALL | |
| 046 | 22 | PA | | 6-0 | SPARE | D05205J | | 46 | | D04525J | 30 | | | ALL | |
| 047 | 22 | PA | | 6-0 | 34-22-23 | D05205J | | 47 | | D04525J | 31 | | | ALL | |
| 201B | 24 | PW | IA | 12-0 | 22-41-11 | D05205J | | 11 | | D05201J | 11 | | | ALL | |
| 201R | 24 | PW | IA | 0-0 | 22-41-11 | D05205J | | 10 | | D05201J | 10 | | | ALL | |
| 201Z | | | IA | 0-0 | 22-41-11 | D05205J | | 12 | | D05201J | 12 | | | ALL | |
| 202B | 24 | PW | IB | 12-0 | 34-22-18 | D05205J | | 14 | | D05201J | 14 | | | ALL | |
| 202R | 24 | PW | IB | 0-0 | 34-22-18 | D05205J | | 13 | | D05201J | 13 | | | ALL | |
| 202Z | | | IB | 0-0 | 34-22-18 | D05205J | | 15 | | D05201J | 15 | | | ALL | |
| 203B | 24 | PW | IC | 12-0 | 34-22-19 | D05205J | | 17 | | D05201J | 17 | | | ALL | |
| 203R | 24 | PW | IC | 0-0 | 34-22-19 | D05205J | | 16 | | D05201J | 16 | | | ALL | |
| 203Z | | | IC | 0-0 | 34-22-19 | D05205J | | 18 | | D05201J | 18 | | | ALL | |
| 204B | 24 | PW | ID | 12-0 | 34-22-19 | D05205J | | 20 | | D05201J | 20 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1500

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1503 | 286T1503 | | | INTERSHELF,L,E1-2 TO SHELVES (continued) | | | | | | | | | | | | |
| 204R | 24 | PW | ID | 0-0 | 34-22-19 | D05205J | 19 | | | | D05201J | 19 | | | ALL | |
| 204Z | | | ID | 0-0 | 34-22-19 | D05205J | 21 | | | | D05201J | 21 | | | ALL | |
| 205B | 24 | PW | IE | 12-0 | 34-61-14 | D05205J | 23 | | | | D05201J | 23 | | | ALL | |
| 205R | 24 | PW | IE | 0-0 | 34-61-14 | D05205J | 22 | | | | D05201J | 22 | | | ALL | |
| 205Z | | | IE | 0-0 | 34-61-14 | D05205J | 24 | | | | D05201J | 24 | | | ALL | |
| 206B | 24 | PW | IF | 12-0 | 34-61-16 | D05205J | 26 | | | | D05201J | 26 | | | ALL | |
| 206R | 24 | PW | IF | 0-0 | 34-61-16 | D05205J | 25 | | | | D05201J | 25 | | | ALL | |
| 206Z | | | IF | 0-0 | SPARE | D05205J | 27 | | | | D05201J | 27 | | | 050-099 | |
| 206Z | | | IF | 0-0 | 34-61-16 | D05205J | 27 | | | | D05201J | 27 | | | 150-199, 275-299 | |
| 207B | 24 | PW | IG | 6-0 | 34-46-11 | D05205J | 29 | | | | D04525J | 2 | | | ALL | |
| 207R | 24 | PW | IG | 0-0 | 34-46-11 | D05205J | 28 | | | | D04525J | 1 | | | ALL | |
| 207Z | | | IG | 0-0 | 34-46-11 | D05205J | 30 | | | | D04525J | 3 | | | ALL | |
| 208B | 24 | PW | IH | 6-0 | SPARE | D05205J | 32 | | | | D04525J | 10 | | | ALL | |
| 208R | 24 | PW | IH | 0-0 | SPARE | D05205J | 31 | | | | D04525J | 9 | | | 050-099, 150-199, 275-278 | |
| 208R | 24 | PW | IH | 0-0 | 34-46-12 | D05205J | 31 | | | | D04525J | 9 | | | 280-299 | |
| 208Z | | | IH | 0-0 | SPARE | D05205J | 33 | | | | D04525J | 11 | | | 050-099, 150-199, 275-278 | |
| 208Z | | | IH | 0-0 | 34-46-12 | D05205J | 33 | | | | D04525J | 11 | | | 280-299 | |
| 210B | 24 | PW | IJ | 6-0 | 22-41-12 | D04525J | 19 | | | | D05205J | 39 | | | ALL | |
| 210R | 24 | PW | IJ | 0-0 | 22-41-12 | D04525J | 18 | | | | D05205J | 38 | | | ALL | |
| 210Z | | | IJ | 0-0 | 22-41-12 | D04525J | 20 | | | | D05205J | 40 | | | ALL | |
| 211B | 24 | PW | IK | 6-0 | 34-46-11 | D04525J | 22 | | | | D05205J | 42 | | | ALL | |
| 211R | 24 | PW | IK | 0-0 | 34-46-11 | D04525J | 21 | | | | D05205J | 41 | | | ALL | |
| 211Z | | | IK | 0-0 | 34-46-11 | D04525J | 23 | | | | D05205J | 43 | | | ALL | |
| 212B | 24 | PW | IL | 12-0 | SPARE | D05205J | 50 | | | | D05201J | 30 | | | 150-199 | |
| 212R | 24 | PW | IL | 0-0 | SPARE | D05205J | 49 | | | | D05201J | 29 | | | 150-199 | |
| 212Z | | | IL | 0-0 | SPARE | D05205J | 51 | | | | D05201J | 31 | | | 150-199 | |
| 213B | 24 | PW | IM | 6-0 | 34-22-19 | D05205J | 53 | | | | D04525J | 26 | | | ALL | |
| 213R | 24 | PW | IM | 0-0 | 34-22-19 | D05205J | 52 | | | | D04525J | 25 | | | ALL | |
| 213Z | | | IM | 0-0 | 34-22-19 | D05205J | 54 | | | | D04525J | 27 | | | ALL | |
| 900B | 24 | PW | IO | 6-0 | 34-46-11 | D04525J | 13 | | | | D04292J | 29 | | | 050-099, 150-166, 275-299 | |
| 900R | 24 | PW | IO | 0-0 | 34-46-11 | D04525J | 12 | | | | D04292J | 28 | | | 050-099, 150-166, 275-299 | |
| 900Z | | | IO | 0-0 | 34-46-11 | D04525J | 14 | | | | D04292J | 30 | | | 050-099, 150-166, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W1500
Page 3
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | To | | | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1505 | 286T1505 | | | | INTERSHELF L E1-3,E1-5 | | | | | | | | | | | |
| 001 | 24 | | PK | | 18-0 | SPARE | D04941J | | 4 | | | D04943J | | 4 | | ALL |
| 002 | 24 | | PK | | 18-0 | SPARE | D04941J | | 5 | | | D04943J | | 5 | | ALL |
| 201B | 24 | | PW | IA | 18-0 | 31-31-14 | D04941J | | 1 | | | D04943J | | 1 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 31-31-14 | D04941J | | 2 | | | D04943J | | 2 | | ALL |
| 201Z | | | | IA | 0-0 | 31-31-14 | D04941J | | 3 | | | D04943J | | 3 | | ALL |
| 202B | 24 | | PW | IB | 18-0 | SPARE | D04941J | | 6 | | | D04943J | | 6 | | ALL |
| 202R | 24 | | PW | IB | 0-0 | SPARE | D04941J | | 7 | | | D04943J | | 7 | | ALL |
| 202Z | | | | IB | 0-0 | SPARE | D04941J | | 8 | | | D04943J | | 8 | | ALL |
| 203B | 24 | | PW | IC | 18-0 | SPARE | D04941J | | 11 | | | D04943J | | 11 | | 150-199 |
| 203R | 24 | | PW | IC | 0-0 | SPARE | D04941J | | 10 | | | D04943J | | 10 | | 150-199 |
| 203Z | | | | IC | 0-0 | SPARE | D04941J | | 12 | | | D04943J | | 12 | | 150-199 |
| 204B | 24 | | PW | ID | 18-0 | SPARE | D04941J | | 14 | | | D04943J | | 14 | | 150-199 |
| 204R | 24 | | PW | ID | 0-0 | SPARE | D04941J | | 13 | | | D04943J | | 13 | | 150-199 |
| 204Z | | | | ID | 0-0 | SPARE | D04941J | | 15 | | | D04943J | | 15 | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W1500
Page 4 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | To | | | | | | | | |
|------------------------|-----------------|----|----|----------------------------------|-------|----------|---------|------|------|--------|-------|------|------|---------|-------------|--|--|---------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1511 | 286T1511 | | | INTERSHELF R,E1-1 TO E2-1 | | | | | | | | | | | | | | |
| 001 | 22 | | PA | | 11-0 | 22-21-11 | D05549P | | | 1 | | | | D05489P | 1 | | | ALL |
| 002 | 22 | | PA | | 11-0 | 22-21-11 | D05549P | | | 2 | | | | D05489P | 2 | | | ALL |
| 003 | 22 | | PA | | 11-0 | 22-21-21 | D05549P | | | 3 | | | | D05489P | 3 | | | ALL |
| 004 | 22 | | PA | | 11-0 | 27-09-14 | D05549P | | | 4 | | | | D05489P | 4 | | | ALL |
| 005 | 22 | | PA | | 11-0 | SPARE | D05549P | | | 5 | | | | D05489P | 5 | | | ALL |
| 006 | 22 | | PA | | 11-0 | SPARE | D05549P | | | 6 | | | | D05489P | 6 | | | ALL |
| 007 | 22 | | PA | | 11-0 | 22-22-11 | D05549P | | | 7 | | | | D05489P | 7 | | | ALL |
| 008 | 22 | | PA | | 11-0 | 22-24-11 | D05549P | | | 8 | | | | D05489P | 8 | | | ALL |
| 009 | 22 | | PA | | 11-0 | 22-24-11 | D05549P | | | 9 | | | | D05489P | 9 | | | ALL |
| 010 | 22 | | PA | | 11-0 | 22-24-11 | D05549P | | | 10 | | | | D05489P | 10 | | | ALL |
| 011 | 22 | | PA | | 11-0 | 27-09-12 | D05549P | | | 11 | | | | D05489P | 11 | | | ALL |
| 012 | 22 | | PA | | 11-0 | 27-09-13 | D05549P | | | 12 | | | | D05489P | 12 | | | ALL |
| 013 | 22 | | PA | | 11-0 | 27-09-13 | D05549P | | | 13 | | | | D05489P | 13 | | | ALL |
| 014 | 22 | | PA | | 11-0 | SPARE | D05549P | | | 14 | | | | D05489P | 14 | | | ALL |
| 015 | 22 | | PA | | 11-0 | 27-41-11 | D05549P | | | 15 | | | | D05489P | 15 | | | ALL |
| 016 | 22 | | PA | | 11-0 | 27-41-11 | D05549P | | | 16 | | | | D05489P | 16 | | | ALL |
| 017 | 22 | | PA | | 11-0 | 27-11-22 | D05549P | | | 17 | | | | D05489P | 17 | | | ALL |
| 018 | 22 | | PA | | 11-0 | 27-11-22 | D05549P | | | 18 | | | | D05489P | 18 | | | ALL |
| 019 | 22 | | PA | | 11-0 | 27-41-11 | D05549P | | | 19 | | | | D05489P | 19 | | | ALL |
| 020 | 22 | | PA | | 11-0 | 27-61-11 | D05549P | | | 20 | | | | D05489P | 20 | | | ALL |
| 021 | 22 | | PA | | 11-0 | 27-61-12 | D05549P | | | 21 | | | | D05489P | 21 | | | ALL |
| 022 | 22 | | PA | | 11-0 | 27-09-14 | D05549P | | | 22 | | | | D05489P | 22 | | | ALL |
| 023 | 22 | | PA | | 11-0 | 27-41-11 | D05549P | | | 23 | | | | D05489P | 23 | | | ALL |
| 024 | 22 | | PA | | 9-0 | SPARE | D05407J | | | 18 | | | | D05489P | 24 | | | ALL |
| 025 | 22 | | PA | | 9-0 | SPARE | D05407J | | | 19 | | | | D05489P | 25 | | | ALL |
| 030 | 22 | | PA | | 11-0 | 27-21-12 | D05549P | | | 30 | | | | D05489P | 30 | | | ALL |
| 031 | 22 | | PA | | 11-0 | 27-21-12 | D05549P | | | 31 | | | | D05489P | 31 | | | ALL |
| 037 | 22 | | PA | | 11-0 | 27-21-12 | D05549P | | | 37 | | | | D05489P | 37 | | | ALL |
| 038 | 22 | | PA | | 11-0 | 27-21-12 | D05549P | | | 38 | | | | D05489P | 38 | | | ALL |
| 039 | 22 | | PA | | 11-0 | 27-21-12 | D05549P | | | 39 | | | | D05489P | 39 | | | ALL |
| 042 | 22 | | PA | | 11-0 | 27-41-11 | D05549P | | | 42 | | | | D05489P | 42 | | | ALL |
| 043 | 22 | | PA | | 11-0 | 27-41-11 | D05549P | | | 43 | | | | D05489P | 43 | | | ALL |
| 044 | 22 | | PA | | 11-0 | SPARE | D05549P | | | 44 | | | | D05489P | 44 | | | ALL |
| 045 | 22 | | PA | | 13-0 | 27-09-14 | D05549P | | | 45 | | | | D05407J | 1 | | | ALL |
| 046 | 22 | | PA | | 13-0 | 27-09-14 | D05549P | | | 46 | | | | D05407J | 6 | | | ALL |
| 047 | 22 | | PA | | 13-0 | 27-09-14 | D05549P | | | 47 | | | | D05407J | 2 | | | ALL |
| 048 | 22 | | PA | | 12-0 | SPARE | D05549P | | | 48 | | | | D05397J | 8 | | | ALL |
| 049 | 22 | | PA | | 12-0 | SPARE | D05549P | | | 49 | | | | D05397J | 9 | | | ALL |
| 050 | 22 | | PA | | 12-0 | SPARE | D05549P | | | 50 | | | | D05397J | 10 | | | 050-099 |

WIRE LIST

D280T132

91-21-11
Section W1510
Page 1
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1511 | 286T1511 | | | INTERSHELF R,E1-1 TO E2-1 (continued) | | | | | | | | | | | | |
| 050 | 22 | | PA | 12-0 | SPARE | D05549P | | CAP | Y | | D05397J | 10 | | | 150-199, 275-299 | |
| 059 | 22 | | PA | 10-0 | 27-09-14 | D05407J | | 17 | | | D05489P | 49 | | | ALL | |
| 201B | 24 | | PW IA | 12-0 | 22-21-11 | D05549P | | 25 | | | D05397J | 5 | | | ALL | |
| 201R | 24 | | PW IA | 0-0 | 22-21-11 | D05549P | | 24 | | | D05397J | 4 | | | ALL | |
| 201Z | | | IA | 0-0 | 22-21-11 | D05549P | | 26 | | | D05397J | 6 | | | ALL | |
| 202B | 24 | | PW IB | 13-0 | 27-11-12 | D05549P | | 28 | | | D05407J | 8 | | | ALL | |
| 202R | 24 | | PW IB | 0-0 | 27-11-12 | D05549P | | 27 | | | D05407J | 7 | | | ALL | |
| 202Z | | | IB | 0-0 | 27-11-12 | D05549P | | 29 | | | D05407J | 9 | | | ALL | |
| 203B | 22 | | PB IC | 11-0 | 27-21-12 | D05549P | | 36 | | | D05489P | 36 | | | ALL | |
| 203R | 22 | | PB IC | 0-0 | 27-21-12 | D05549P | | 35 | | | D05489P | 35 | | | ALL | |
| 204B | 24 | | PW ID | 12-0 | SPARE | D05549P | | 52 | | | D05397J | 2 | | | ALL | |
| 204R | 24 | | PW ID | 0-0 | SPARE | D05549P | | 51 | | | D05397J | 1 | | | ALL | |
| 204Z | | | ID | 0-0 | SPARE | D05549P | | 33 | | | D05397J | 3 | | | ALL | |
| 205B | 24 | | PW IE | 13-0 | SPARE | D05549P | | 54 | | | D05407J | 4 | | | ALL | |
| 205R | 24 | | PW IE | 0-0 | SPARE | D05549P | | 53 | | | D05407J | 3 | | | ALL | |
| 205Z | | | IE | 0-0 | SPARE | D05549P | | 55 | | | D05407J | 5 | | | ALL | |
| 206B | 22 | | PB IF | 13-0 | 31-51-43 | D05549P | | 41 | | | D05407J | 11 | | | ALL | |
| 206R | 22 | | PB IF | 0-0 | 31-51-43 | D05549P | | 40 | | | D05407J | 10 | | | ALL | |
| 207B | 24 | | PW IG | 16-0 | 22-21-31 | D05549P | | 34 | | | D05489P | 28 | | | 150-199, 275-299 | |
| 207R | 24 | | PW IG | 0-0 | 22-21-31 | D05549P | | 32 | | | D05489P | 27 | | | 150-199, 275-299 | |
| 207Z | | | IG | 0-0 | 22-21-31 | D05549P | | 50 | | | D05489P | 26 | | | 150-199, 275-299 | |
| 208B | 24 | | PW IH | 10-0 | 22-21-31 | D05407J | | 13 | | | D05489P | 34 | | | 150-199, 275-299 | |
| 208R | 24 | | PW IH | 0-0 | 22-21-31 | D05407J | | 12 | | | D05489P | 33 | | | 150-199, 275-299 | |
| 208Z | | | IH | 0-0 | 22-21-31 | D05407J | | 14 | | | D05489P | 32 | | | 150-199, 275-299 | |
| W1513 | 286T1513 | | | INTERSHELF R,E1-2 TO SHELVES | | | | | | | | | | | | |
| 001 | 22 | | PA | 6-0 | SPARE | D04873J | | 1 | | | D04875J | 1 | | | 050-099 | |
| 001 | 22 | | PA | 6-0 | 34-22-13 | D04873J | | 1 | | | D04875J | 1 | | | 150-199, 275-299 | |
| 002 | 22 | | PA | 6-0 | 22-41-11 | D04873J | | 2 | | | D04875J | 2 | | | ALL | |
| 003 | 22 | | PA | 14-0 | SPARE | D04339J | | 20 | | | D04875J | 20 | | | ALL | |
| 004 | 22 | | PA | 4-0 | SPARE | D05529J | | 4 | | | D04875J | 34 | | | ALL | |
| 005 | 22 | | PA | 4-0 | SPARE | D05529J | | 5 | | | D04875J | 35 | | | 050-099 | |
| 009 | 24 | | PK | 17-0 | 31-31-26 | D04875J | | 27 | | | D04339J | 21 | | | 050-099 | |
| 009 | 24 | | PK | 14-0 | 31-31-26 | D04875J | | 27 | | | D04339J | 21 | | | 150-199, 275-299 | |
| 012 | 24 | | PK | 14-0 | SPARE | D04339J | | 12 | | | D04875J | 32 | | | 050-099 | |
| 201B | 24 | | PW IA | 4-0 | 22-12-21 | D05529J | | 10 | | | D04875J | 10 | | | ALL | |
| 201R | 24 | | PW IA | 0-0 | 22-12-21 | D05529J | | 9 | | | D04875J | 9 | | | ALL | |
| 201Z | | | IA | 0-0 | 22-12-21 | D05529J | | 11 | | | D04875J | 11 | | | ALL | |
| 202B | 24 | | PW IB | 14-0 | 22-41-11 | D04339J | | 3 | | | D04875J | 13 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1510

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1513 | 286T1513 | | | INTERSHELF R,E1-2 TO SHELVES (continued) | | | | | | | | | | | |
| 202R | 24 | PW | IB | 0-0 | 22-41-11 | D04339J | | 2 | | D04875J | | 12 | | ALL | |
| 202Z | | | IB | 0-0 | 22-41-11 | D04339J | | 4 | | D04875J | | 14 | | ALL | |
| 203B | 24 | PW | IC | 6-0 | 22-41-11 | D04873J | | 4 | | D04875J | | 4 | | ALL | |
| 203R | 24 | PW | IC | 0-0 | 22-41-11 | D04873J | | 3 | | D04875J | | 3 | | ALL | |
| 203Z | | | IC | 0-0 | 22-41-11 | D04873J | | 5 | | D04875J | | 5 | | ALL | |
| 205B | 24 | PW | IE | 6-0 | SPARE | D04873J | | 10 | | D04875J | | 16 | | 050-099 | |
| 205R | 24 | PW | IE | 0-0 | SPARE | D04873J | | 9 | | D04875J | | 15 | | 050-099 | |
| 205Z | | | IE | 0-0 | SPARE | D04873J | | 11 | | D04875J | | 17 | | 050-099 | |
| 207W | 24 | 7K | IG | 4-0 | 34-43-11 | D05529J | | 1 | | D04875J | | 21 | | ALL | |
| 207WB | 24 | 7K | IG | 0-0 | 34-43-11 | D05529J | | 2 | | D04875J | | 22 | | ALL | |
| 207Z | | | IG | 0-0 | 34-43-11 | D05529J | | 3 | | D04875J | | 23 | | ALL | |
| 208B | 24 | PW | IH | 6-0 | SPARE | D04873J | | 15 | | D04875J | | 25 | | ALL | |
| 208R | 24 | PW | IH | 0-0 | SPARE | D04873J | | 14 | | D04875J | | 24 | | ALL | |
| 208Z | | | IH | 0-0 | SPARE | D04873J | | 16 | | D04875J | | 26 | | ALL | |
| 211B | 24 | PW | IK | 14-0 | 21-31-11 | D04339J | | 17 | | D04875J | | 7 | | ALL | |
| 211R | 24 | PW | IK | 0-0 | 21-31-11 | D04339J | | 16 | | D04875J | | 6 | | ALL | |
| 211Z | | | IK | 0-0 | 21-31-11 | D04339J | | 18 | | D04875J | | 8 | | ALL | |
| 212B | 24 | PL | IL | 6-0 | 27-32-21 | D04873J | | 19 | | D04875J | | 19 | | ALL | |
| 212R | 24 | PL | IL | 0-0 | 27-32-21 | D04873J | | 18 | | D04875J | | 18 | | ALL | |
| 213B | 24 | PW | IM | 17-0 | 31-31-20 | D04873J | | 7 | | D04339J | | 7 | | ALL | |
| 213R | 24 | PW | IM | 0-0 | 31-31-20 | D04873J | | 6 | | D04339J | | 6 | | ALL | |
| 213Z | | | IM | 0-0 | 31-31-20 | D04873J | | 8 | | D04339J | | 8 | | ALL | |
| 214B | 24 | PW | IN | 17-0 | 31-31-20 | D04873J | | 21 | | D04339J | | 10 | | ALL | |
| 214R | 24 | PW | IN | 0-0 | 31-31-20 | D04873J | | 20 | | D04339J | | 9 | | ALL | |
| 214Z | | | IN | 0-0 | 31-31-20 | D04873J | | 22 | | D04339J | | 11 | | ALL | |
| W1515 | 286T1515 | | | INTERSHELF R, E1-5 TO SHELVES | | | | | | | | | | | |
| 001 | 22 | PA | | 4-0 | 22-14-11 | D04857J | | 1 | | D04859J | | 1 | | ALL | |
| 002 | 22 | PA | | 4-0 | 22-11-22 | D04857J | | 2 | | D04859J | | 2 | | ALL | |
| 003 | 24 | PK | | 4-0 | 22-14-21 | D04857J | | 3 | | D04859J | | 3 | | ALL | |
| 005 | 24 | PK | | 15-0 | SPARE | D04857J | | 5 | | D05861J | | 5 | | ALL | |
| 006 | 24 | PK | | 4-0 | 22-15-12 | D04857J | | 16 | | D04859J | | 16 | | ALL | |
| 007 | 22 | PA | | 4-0 | SPARE | D04857J | | 23 | | D04859J | | 23 | | 050-099, 150-156, 162-166, 275-276 | |
| 007 | 22 | PA | | 4-0 | 34-45-14 | D04857J | | 23 | | D04859J | | 23 | | 157, 167-199, 277-299 | |
| 008 | 22 | PA | | 4-0 | SPARE | D04857J | | 30 | | D04859J | | 30 | | ALL | |
| 009 | 22 | PA | | 4-0 | SPARE | D04857J | | 31 | | D04859J | | 31 | | ALL | |
| 010 | 24 | PK | | 15-0 | SPARE | D04857J | | 32 | | D05861J | | 2 | | ALL | |
| 011 | 24 | PK | | 15-0 | SPARE | D04857J | | 33 | | D05861J | | 3 | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W1510
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1515 | 286T1515 | | | INTERSHELF R, E1-5 TO SHELVES (continued) | | | | | | | | | | | | | |
| 013 | 24 | | PK | 15-0 | 34-33-21 | D04857J | | 41 | | | | | D05861J | 21 | | | ALL |
| 014 | 24 | | PK | 15-0 | SPARE | D04857J | | 39 | | | | | D05861J | 19 | | | 050-099 |
| 015 | 24 | | PK | 15-0 | SPARE | D04857J | | 40 | | | | | D05861J | 20 | | | 050-099 |
| 016 | 24 | | PK | 15-0 | SPARE | D04857J | | 35 | | | | | D05861J | 9 | | | 050-099 |
| 017 | 24 | | PK | 15-0 | SPARE | D04857J | | 36 | | | | | D05861J | 10 | | | 050-099 |
| 018 | 24 | | PK | 15-0 | SPARE | D04857J | | 37 | | | | | D05861J | 11 | | | 050-099 |
| 019 | 24 | | PK | 15-0 | SPARE | D04857J | | 38 | | | | | D05861J | 12 | | | 050-099 |
| 022 | 24 | | PK | 15-0 | 22-12-21 | D04857J | | 45 | | | | | D05861J | 15 | | | ALL |
| 023 | 24 | | PK | 4-0 | 22-15-12 | D04857J | | 44 | | | | | D04859J | 5 | | | ALL |
| 200B | 24 | | PW | HY | 4-0 | 34-45-14 | D04859J | | 21 | | | | D04857J | 53 | | | 050-099, 150-199, 277-299 |
| 200R | 24 | | PW | HY | 0-0 | 34-45-14 | D04859J | | 20 | | | | D04857J | 52 | | | 050-099, 150-199, 277-299 |
| 200Z | | | | HY | 0-0 | 34-45-14 | D04859J | | 22 | | | | D04857J | 54 | | | 050-099, 150-199, 277-299 |
| 201B | 24 | | PW | IA | 4-0 | 22-15-11 | D04857J | | 25 | | | | D04859J | 25 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 22-15-11 | D04857J | | 24 | | | | D04859J | 24 | | | ALL |
| 201Z | | | | IA | 0-0 | 22-15-11 | D04857J | | 26 | | | | D04859J | 26 | | | ALL |
| 202B | 24 | | PW | IB | 4-0 | SPARE | D04857J | | 18 | | | | D04859J | 18 | | | ALL |
| 202R | 24 | | PW | IB | 0-0 | SPARE | D04857J | | 17 | | | | D04859J | 17 | | | ALL |
| 202Z | | | | IB | 0-0 | SPARE | D04857J | | 19 | | | | D04859J | 19 | | | ALL |
| 203B | 24 | | PW | IC | 4-0 | 22-32-12 | D04857J | | 14 | | | | D04859J | 14 | | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 22-32-12 | D04857J | | 13 | | | | D04859J | 13 | | | ALL |
| 203Z | | | | IC | 0-0 | 22-32-12 | D04857J | | 15 | | | | D04859J | 15 | | | ALL |
| 204B | 22 | | PB | ID | 4-0 | SPARE | D04857J | | 10 | | | | D04859J | 10 | | | ALL |
| 204R | 22 | | PB | ID | 0-0 | SPARE | D04857J | | 9 | | | | D04859J | 9 | | | ALL |
| 207B | 24 | | PW | IG | 15-0 | 34-22-29 | D04857J | | 7 | | | | D05861J | 7 | | | ALL |
| 207R | 24 | | PW | IG | 0-0 | 34-22-29 | D04857J | | 6 | | | | D05861J | 6 | | | ALL |
| 207Z | | | | IG | 0-0 | 34-22-29 | D04857J | | 8 | | | | D05861J | 8 | | | ALL |
| 208B | 24 | | PW | IH | 4-0 | SPARE | D04857J | | 28 | | | | D04859J | 28 | | | ALL |
| 208R | 24 | | PW | IH | 0-0 | SPARE | D04857J | | 27 | | | | D04859J | 27 | | | ALL |
| 208Z | | | | IH | 0-0 | SPARE | D04857J | | 29 | | | | D04859J | 29 | | | ALL |
| 209B | 24 | | PW | II | 15-0 | 22-12-21 | D04857J | | 47 | | | | D05861J | 17 | | | ALL |
| 209R | 24 | | PW | II | 0-0 | 22-12-21 | D04857J | | 46 | | | | D05861J | 16 | | | ALL |
| 209Z | | | | II | 0-0 | 22-12-21 | D04857J | | 48 | | | | D05861J | 18 | | | ALL |
| 210B | 24 | | PW | IJ | 15-0 | 34-22-28 | D05861J | | 23 | | | | D04857J | 21 | | | ALL |
| 210R | 24 | | PW | IJ | 0-0 | 34-22-28 | D05861J | | 22 | | | | D04857J | 20 | | | ALL |
| 210Z | | | | IJ | 0-0 | 34-22-28 | D05861J | | 24 | | | | D04857J | 22 | | | ALL |
| 211B | 24 | | PW | IK | 15-0 | 31-35-13 | D04857J | | 43 | | | | D05861J | 14 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1510

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1515 | 286T1515 | | | INTERSHELF R, E1-5 TO SHELVES (continued) | | | | | | | | | | | |
| 211R | 24 | PW | IK | | 0-0 | 31-35-13 | D04857J | | 42 | | D05861J | | 13 | | ALL |
| 211Z | | | IK | | 0-0 | 31-35-13 | D04857J | | 34 | | D05861J | | 4 | | ALL |
| 212B | 24 | PW | IL | | 15-0 | SPARE | D04857J | | 40 | | D05861J | | 20 | | 150-199 |
| 212R | 24 | PW | IL | | 0-0 | SPARE | D04857J | | 39 | | D05861J | | 19 | | 150-199 |
| 212Z | | | IL | | 0-0 | SPARE | D04857J | | 35 | | D05861J | | 9 | | 150-199 |
| 213B | 24 | PW | IM | | 15-0 | SPARE | D04857J | | 37 | | D05861J | | 11 | | 150-199 |
| 213R | 24 | PW | IM | | 0-0 | SPARE | D04857J | | 36 | | D05861J | | 10 | | 150-199 |
| 213Z | | | IM | | 0-0 | SPARE | D04857J | | 38 | | D05861J | | 12 | | 150-199 |
| 301B | 24 | PM | MA | | 4-0 | 34-12-11 | D04857J | | 11 | | D04859J | | 11 | | ALL |
| 301R | 24 | PM | MA | | 0-0 | 34-12-11 | D04857J | | 4 | | D04859J | | 4 | | ALL |
| 301Y | 24 | PM | MA | | 0-0 | 34-12-11 | D04857J | | 12 | | D04859J | | 12 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1510
Page 5 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1521 | 286T1521 | | | INTERSHELF C TO P36 & P37 | | | | | | | | | | | | | |
| 001 | 22 | | PA | 11-0 | 22-22-11 | D04357P | | | 9 | | | | D04355J | 9 | | | ALL |
| 002 | 22 | | PA | 11-0 | SPARE | D04357P | | | 10 | | | | D04355J | 10 | | | ALL |
| 003 | 22 | | PA | 22-0 | SPARE | D04357P | | | 1 | | | | D05319P | 1 | | | ALL |
| 004 | 22 | | PA | 22-0 | 27-09-12 | D04357P | | | 2 | | | | D05319P | 3 | | | ALL |
| 005 | 22 | | PA | 11-0 | SPARE | D04357P | | | 11 | | | | D04355J | 11 | | | ALL |
| 006 | 20 | | PA | 22-0 | SPARE | D04357P | | | 12 | | | | D05319P | 2 | | | ALL |
| 008 | 22 | | PA | 14-0 | 27-09-13 | D04357P | | | 14 | | | | D05313P | 5 | | | ALL |
| 009 | 22 | | PA | 11-0 | 22-24-11 | D04357P | | | 15 | | | | D04355J | 1 | | | ALL |
| 010 | 22 | | PA | 11-0 | 27-61-11 | D04357P | | | 16 | | | | D04355J | 2 | | | ALL |
| 011 | 22 | | PA | 14-0 | 27-09-13 | D04357P | | | 17 | | | | D05313P | 2 | | | ALL |
| 012 | 22 | | PA | 14-0 | 27-09-13 | D04357P | | | 18 | | | | D05313P | 4 | | | ALL |
| 013 | 22 | | PA | 11-0 | 22-21-11 | D04357P | | | 22 | | | | D04355J | 22 | | | ALL |
| 014 | 22 | | PA | 11-0 | 22-22-11 | D04357P | | | 7 | | | | D04355J | 7 | | | ALL |
| 015 | 22 | | PA | 11-0 | 22-22-11 | D04357P | | | 8 | | | | D04355J | 8 | | | ALL |
| 201B | 22 | | PR | JA | 11-0 | 22-22-11 | D04357P | | 4 | | | | D04355J | 4 | | | ALL |
| 201R | 22 | | PR | JA | 0-0 | 22-22-11 | D04357P | | 3 | | | | D04355J | 3 | | | ALL |
| 201Z | | | | JA | 0-0 | 22-22-11 | D04357P | | 5 | | | | D04355J | 5 | | | ALL |
| 203B | 24 | | PW | IC | 11-0 | 22-21-11 | D04357P | | 21 | | | | D04355J | 21 | | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 22-21-11 | D04357P | | 20 | | | | D04355J | 20 | | | ALL |
| 203Z | | | | IC | 0-0 | 22-21-11 | D04357P | | 19 | | | | D04355J | 19 | | | ALL |
| 204B | 24 | | PL | ID | 11-0 | 22-12-31 | D04357P | | 24 | | | | D04355J | 24 | | | ALL |
| 204R | 24 | | PL | ID | 0-0 | 22-12-31 | D04357P | | 23 | | | | D04355J | 23 | | | ALL |
| 241B | 24 | | PW | JP | 11-0 | 32-45-13 | D04355J | | 13 | | | | D04357P | 25 | | | 050-099, 150-199 |
| 241R | 24 | | PW | JP | 0-0 | 32-45-13 | D04355J | | 14 | | | | D04357P | 26 | | | 050-099, 150-199 |
| 241Z | | | | JP | 0-0 | 32-45-13 | D04355J | | 15 | | | | D04357P | 6 | | | 050-099, 150-199 |
| 242B | 24 | | PW | JQ | 11-0 | 32-45-13 | D04355J | | 16 | | | | D04357P | 27 | | | 050-099, 150-199 |
| 242R | 24 | | PW | JQ | 0-0 | 32-45-13 | D04355J | | 17 | | | | D04357P | 28 | | | 050-099, 150-199 |
| 242Z | | | | JQ | 0-0 | 32-45-13 | D04355J | | 18 | | | | D04357P | 13 | | | 050-099, 150-199 |
| 243B | 24 | | PW | JR | 11-0 | 32-45-13 | D04355J | | 28 | | | | D04357P | 29 | | | 050-099, 150-199 |
| 243R | 24 | | PW | JR | 0-0 | 32-45-13 | D04355J | | 29 | | | | D04357P | 30 | | | 050-099, 150-199 |
| 243Z | | | | JR | 0-0 | 32-45-13 | D04355J | | 30 | | | | D04357P | 31 | | | 050-099, 150-199 |
| 244B | 24 | | PW | JS | 11-0 | 32-45-13 | D04355J | | 31 | | | | D04357P | 32 | | | 050-099, 150-199 |
| 244R | 24 | | PW | JS | 0-0 | 32-45-13 | D04355J | | 32 | | | | D04357P | 33 | | | 050-099, 150-199 |
| 244Z | | | | JS | 0-0 | 32-45-13 | D04355J | | 33 | | | | D04357P | 34 | | | 050-099, 150-199 |
| W1523 | 286T1523 | | | INTERSHELF C E1-2,E1-4,E1-6,E8 DELTA | | | | | | | | | | | | | |
| 001 | 22 | | PA | 6-0 | SPARE | D04915J | | | 16 | | | | D04913J | 16 | | | ALL |
| 002 | 22 | | PA | 6-0 | SPARE | D04913J | | | 24 | | | | D04915J | 4 | | | ALL |
| 005 | 22 | | PA | 8-0 | 34-22-17 | D04915J | | | 6 | | | | D04969J | 16 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1520

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1523 | 286T1523 | | | INTERSHELF C E1-2,E1-4,E1-6,E8 DELTA (continued) | | | | | | | | | | | |
| 006 | 24 | | PK | | 5-0 | 34-21-31 | D04913J | 20 | | | D04969J | 20 | | | ALL |
| 010 | 22 | | PA | | 5-0 | 22-21-11 | D04913J | 35 | | | D04969J | 25 | | | ALL |
| 011 | 22 | | PA | | 5-0 | 34-22-37 | D04913J | 9 | | | D04969J | 13 | | | ALL |
| 012 | 22 | | PA | | 5-0 | SPARE | D04913J | 17 | | | D04969J | 14 | | | ALL |
| 013 | 22 | | PA | | 5-0 | SPARE | D04913J | 18 | | | D04969J | 15 | | | ALL |
| 034 | 22 | | PA | | 5-0 | 34-21-31 | D04913J | 42 | | | D04969J | 32 | | | ALL |
| 035 | 22 | | PA | | 5-0 | 34-21-31 | D04913J | 43 | | | D04969J | 33 | | | ALL |
| 036 | 22 | | PA | | 5-0 | 34-21-31 | D04913J | 44 | | | D04969J | 34 | | | ALL |
| 201B | 24 | | PW | IA | 6-0 | 22-12-31 | D04913J | 11 | | | D04915J | 11 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 22-12-31 | D04913J | 10 | | | D04915J | 10 | | | ALL |
| 201Z | | | | IA | 0-0 | 22-12-31 | D04913J | 12 | | | D04915J | 12 | | | ALL |
| 202B | 24 | | PW | IB | 5-0 | SPARE | D04969J | 2 | | | D04913J | 2 | | | ALL |
| 202R | 24 | | PW | IB | 0-0 | SPARE | D04969J | 1 | | | D04913J | 1 | | | ALL |
| 202Z | | | | IB | 0-0 | SPARE | D04969J | 3 | | | D04913J | 3 | | | ALL |
| 203B | 24 | | PW | IC | 6-0 | 22-41-11 | D04915J | 14 | | | D04913J | 14 | | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 22-41-11 | D04915J | 13 | | | D04913J | 13 | | | ALL |
| 203Z | | | | IC | 0-0 | 22-41-11 | D04915J | 15 | | | D04913J | 15 | | | ALL |
| 205B | 24 | | PW | IE | 8-0 | 34-43-11 | D04915J | 8 | | | D04969J | 8 | | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 34-43-11 | D04915J | 7 | | | D04969J | 7 | | | ALL |
| 205Z | | | | IE | 0-0 | 34-43-11 | D04915J | 9 | | | D04969J | 9 | | | ALL |
| 206B | 24 | | PW | IF | 5-0 | 34-22-38 | D04913J | 5 | | | D04969J | 5 | | | ALL |
| 206R | 24 | | PW | IF | 0-0 | 34-22-38 | D04913J | 4 | | | D04969J | 4 | | | ALL |
| 206Z | | | | IF | 0-0 | 34-22-38 | D04913J | 6 | | | D04969J | 6 | | | ALL |
| 207B | 24 | | PW | IG | 6-0 | SPARE | D04913J | 22 | | | D04915J | 2 | | | ALL |
| 207R | 24 | | PW | IG | 0-0 | SPARE | D04913J | 21 | | | D04915J | 1 | | | ALL |
| 207Z | | | | IG | 0-0 | SPARE | D04913J | 23 | | | D04915J | 3 | | | ALL |
| 208B | 24 | | PW | IH | 6-0 | SPARE | D04913J | 26 | | | D04915J | 26 | | | ALL |
| 208R | 24 | | PW | IH | 0-0 | SPARE | D04913J | 25 | | | D04915J | 25 | | | ALL |
| 208Z | | | | IH | 0-0 | SPARE | D04913J | 27 | | | D04915J | 27 | | | ALL |
| 209B | 24 | | PW | II | 5-0 | 32-42-11 | D04913J | 37 | | | D04969J | 37 | | | ALL |
| 209R | 24 | | PW | II | 0-0 | 32-42-11 | D04913J | 36 | | | D04969J | 36 | | | ALL |
| 209Z | | | | II | 0-0 | 32-42-11 | D04913J | 38 | | | D04969J | 38 | | | ALL |
| 211B | 24 | | PW | IK | 5-0 | 22-21-11 | D04913J | 34 | | | D04969J | 24 | | | ALL |
| 211R | 24 | | PW | IK | 0-0 | 22-21-11 | D04913J | 33 | | | D04969J | 23 | | | ALL |
| 211Z | | | | IK | 0-0 | 22-21-11 | D04913J | 32 | | | D04969J | 22 | | | ALL |
| 212B | 24 | | PW | IL | 5-0 | 34-22-81 | D04913J | 40 | | | D04969J | 40 | | | ALL |
| 212R | 24 | | PW | IL | 0-0 | 34-22-81 | D04913J | 39 | | | D04969J | 39 | | | ALL |
| 212Z | | | | IL | 0-0 | 34-22-81 | D04913J | 41 | | | D04969J | 41 | | | ALL |
| 213B | 24 | | PW | IM | 8-0 | 34-22-18 | D04915J | 21 | | | D04969J | 11 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1520
Page 2
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1523 | 286T1523 | | | INTERSHELF C E1-2,E1-4,E1-6,E8 DELTA (continued) | | | | | | | | | | | | |
| 213R | 24 | PW | IM | 0-0 | 34-22-18 | D04915J | 20 | | | | D04969J | 10 | | | ALL | |
| 213Z | | | IM | 0-0 | 34-22-18 | D04915J | 22 | | | | D04969J | 12 | | | ALL | |
| 214B | 24 | PW | IN | 5-0 | 31-35-13 | D04913J | 29 | | | | D04969J | 27 | | | ALL | |
| 214R | 24 | PW | IN | 0-0 | 31-35-13 | D04913J | 28 | | | | D04969J | 26 | | | ALL | |
| 214Z | | | IN | 0-0 | 31-35-13 | D04913J | 30 | | | | D04969J | 28 | | | ALL | |
| 563B | 24 | PW | WM | 6-0 | 32-45-14 | D04913J | 45 | | | | D04915J | 23 | | | 050-099, 150-199 | |
| 563R | 24 | PW | WM | 0-0 | 32-45-14 | D04913J | 46 | | | | D04915J | 24 | | | 050-099, 150-199 | |
| 563Z | | | WM | 0-0 | 32-45-14 | D04913J | 31 | | | | D04915J | 28 | | | 050-099, 150-199 | |
| 564B | 24 | PW | WN | 6-0 | 32-45-14 | D04913J | 47 | | | | D04915J | 29 | | | 050-099, 150-199 | |
| 564R | 24 | PW | WN | 0-0 | 32-45-14 | D04913J | 48 | | | | D04915J | 30 | | | 050-099, 150-199 | |
| 564Z | | | WN | 0-0 | 32-45-14 | D04913J | 49 | | | | D04915J | 31 | | | 050-099, 150-199 | |
| 565B | 24 | PW | WO | 6-0 | 32-45-14 | D04913J | 50 | | | | D04915J | 32 | | | 050-099, 150-199 | |
| 565R | 24 | PW | WO | 0-0 | 32-45-14 | D04913J | 51 | | | | D04915J | 33 | | | 050-099, 150-199 | |
| 565Z | | | WO | 0-0 | 32-45-14 | D04913J | 52 | | | | D04915J | 34 | | | 050-099, 150-199 | |
| 566B | 24 | PW | WP | 6-0 | 32-45-14 | D04913J | 53 | | | | D04915J | 35 | | | 050-099, 150-199 | |
| 566R | 24 | PW | WP | 0-0 | 32-45-14 | D04913J | 54 | | | | D04915J | 36 | | | 050-099, 150-199 | |
| 566Z | | | WP | 0-0 | 32-45-14 | D04913J | 55 | | | | D04915J | 37 | | | 050-099, 150-199 | |
| W1527 | 286T1527 | | | INTERSHELF E1-4 TO E2-4 | | | | | | | | | | | | |
| 001 | 22 | PA | | 4-0 | SPARE | D04333J | 1 | | | | D04331J | 1 | | | ALL | |
| 002 | 22 | PA | | 4-0 | SPARE | D04333J | 2 | | | | D04331J | 2 | | | ALL | |
| 006 | 22 | PA | | 4-0 | SPARE | D04333J | 6 | | | | D04331J | 6 | | | ALL | |
| 010 | 22 | PA | | 4-0 | SPARE | D04333J | 10 | | | | D04331J | 10 | | | 050-099, 275-299 | |
| 011 | 22 | PA | | 4-0 | SPARE | D04333J | 11 | | | | D04343J | 1 | | | 150-199, 275-299 | |
| 012 | 22 | PA | | 4-0 | SPARE | D04333J | 12 | | | | D04343J | 2 | | | 150-199, 275-299 | |
| 016 | 22 | PA | | 4-0 | SPARE | D04333J | 16 | | | | D04343J | 6 | | | 150-199, 275-299 | |
| 017 | 22 | PA | | 3-0 | 31-31-22 | D04331J | 21 | | | | D04343J | 16 | | | ALL | |
| 018 | 24 | PK | | 3-0 | 31-31-26 | D04331J | 22 | | | | D04343J | 17 | | | ALL | |
| 020 | 24 | PK | | 3-0 | 31-31-26 | D04331J | 17 | | | | D04343J | 18 | | | ALL | |
| 201B | 24 | PW | IA | 4-0 | SPARE | D04333J | 8 | | | | D04331J | 8 | | | 050-099, 275-299 | |
| 201R | 24 | PW | IA | 0-0 | SPARE | D04333J | 7 | | | | D04331J | 7 | | | 050-099, 275-299 | |
| 201Z | | | IA | 0-0 | SPARE | D04333J | 9 | | | | D04331J | 9 | | | 050-099, 275-299 | |
| 202B | 24 | PW | IB | 4-0 | 31-31-20 | D04333J | 4 | | | | D04343J | 4 | | | ALL | |
| 202R | 24 | PW | IB | 0-0 | 31-31-20 | D04333J | 3 | | | | D04343J | 3 | | | ALL | |
| 202Z | | | IB | 0-0 | 31-31-20 | D04333J | 5 | | | | D04343J | 5 | | | ALL | |
| 203B | 24 | PW | IC | 4-0 | 34-12-61 | D04333J | 13 | | | | D04331J | 3 | | | ALL | |
| 203R | 24 | PW | IC | 0-0 | 34-12-61 | D04333J | 14 | | | | D04331J | 4 | | | ALL | |
| 203Z | | | IC | 0-0 | 34-12-61 | D04333J | 15 | | | | D04331J | 5 | | | ALL | |
| 204B | 24 | PW | ID | 4-0 | 31-31-20 | D04333J | 18 | | | | D04343J | 8 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1520

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|----|----|--|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W1527 | 286T1527 | | | INTERSHELF E1-4 TO E2-4 (continued) | | | | | | | | | | | | | | | |
| 204R | 24 | | PW | ID | 0-0 | 31-31-20 | D04333J | | | | 17 | | | | D04343J | 7 | | | ALL |
| 204Z | | | | ID | 0-0 | 31-31-20 | D04333J | | | | 19 | | | | D04343J | 9 | | | ALL |
| 205B | 24 | | PW | IE | 3-0 | 28-41-11 | D04343J | | | | 23 | | | | D04331J | 24 | | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 28-41-11 | D04343J | | | | 22 | | | | D04331J | 23 | | | ALL |
| 205Z | | | | IE | 0-0 | 28-41-11 | D04343J | | | | 24 | | | | D04331J | 25 | | | ALL |
| 206B | 24 | | PW | IF | 3-0 | 31-41-35 | D04343J | | | | 20 | | | | D04331J | 26 | | | ALL |
| 206R | 24 | | PW | IF | 0-0 | 31-41-35 | D04343J | | | | 19 | | | | D04331J | 27 | | | ALL |
| 206Z | | | | IF | 0-0 | 31-41-35 | D04343J | | | | 21 | | | | D04331J | 28 | | | ALL |
| 207B | 24 | | PW | IG | 4-0 | 31-31-20 | D04333J | | | | 22 | | | | D04343J | 12 | | | ALL |
| 207R | 24 | | PW | IG | 0-0 | 31-31-20 | D04333J | | | | 21 | | | | D04343J | 11 | | | ALL |
| 207Z | | | | IG | 0-0 | 31-31-20 | D04333J | | | | 20 | | | | D04343J | 10 | | | ALL |
| 208B | 22 | | PR | IH | 3-0 | 31-31-22 | D04331J | | | | 19 | | | | D04343J | 14 | | | ALL |
| 208R | 22 | | PR | IH | 0-0 | 31-31-22 | D04331J | | | | 18 | | | | D04343J | 13 | | | ALL |
| 208Z | | | | IH | 0-0 | 31-31-22 | D04331J | | | | 20 | | | | D04343J | 15 | | | ALL |
| 301B | 18 | | PS | MR | 3-0 | 31-31-25 | D04331J | | | | 12 | DK | | | D04343J | 26 | DL | | 050-099 |
| 301B | 18 | | PS | MA | 3-0 | 31-31-25 | D04331J | | | | 12 | DK | | | D04343J | 26 | DL | | 150-199, 275-299 |
| 301R | 18 | | PS | MR | 0-0 | 31-31-25 | D04331J | | | | 13 | DK | | | D04343J | 25 | DL | | 050-099 |
| 301R | 18 | | PS | MA | 0-0 | 31-31-25 | D04331J | | | | 13 | DK | | | D04343J | 25 | DL | | 150-199, 275-299 |
| 301Y | 18 | | PS | MR | 0-0 | 31-31-25 | D04331J | | | | 14 | DK | | | D04343J | 27 | DL | | 050-099 |
| 301Y | 18 | | PS | MA | 0-0 | 31-31-25 | D04331J | | | | 14 | DK | | | D04343J | 27 | DL | | 150-199, 275-299 |
| 301Z | | | | MR | 0-0 | 31-31-25 | D04331J | | | | 15 | | | | D04343J | 28 | | | 050-099 |
| 301Z | | | | MA | 0-0 | 31-31-25 | D04331J | | | | 15 | | | | D04343J | 28 | | | 150-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1520
Page 4 End
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|--|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1533 | 286T1533 | | | INTERSHELF L E2-2 TO SHELVES | | | | | | | | | | | | | | |
| 002 | 22 | | PA | | 14-0 | SPARE | D04721J | | 5 | | | | D05573J | | 5 | | | ALL |
| 003 | 22 | | PA | | 14-0 | SPARE | D04721J | | 6 | | | | D05573J | | 6 | | | ALL |
| 004 | 22 | | PA | | 14-0 | SPARE | D04721J | | 7 | | | | D05573J | | 7 | | | ALL |
| 005 | 22 | | PA | | 14-0 | SPARE | D04721J | | 8 | | | | D05573J | | 8 | | | ALL |
| 006 | 22 | | PA | | 14-0 | SPARE | D04721J | | 9 | | | | D05573J | | 9 | | | ALL |
| 007 | 22 | | PA | | 14-0 | SPARE | D04721J | | 14 | | | | D05573J | | 4 | | | ALL |
| 201B | 24 | | PW | IA | 14-0 | 34-46-11 | D04721J | | 2 | | | | D05573J | | 2 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-46-11 | D04721J | | 1 | | | | D05573J | | 1 | | | ALL |
| 201Z | | | | IA | 0-0 | 34-46-11 | D04721J | | 3 | | | | D05573J | | 3 | | | ALL |
| 212B | 24 | | PW | IL | 14-0 | 34-61-14 | D05573J | | 11 | | | | D04721J | | 11 | | | ALL |
| 212R | 24 | | PW | IL | 0-0 | 34-61-14 | D05573J | | 10 | | | | D04721J | | 10 | | | ALL |
| 212Z | | | | IL | 0-0 | 34-61-14 | D05573J | | 12 | | | | D04721J | | 12 | | | ALL |
| 213B | 24 | | PW | IM | 14-0 | SPARE | D04721J | | 17 | | | | D05573J | | 17 | | | ALL |
| 213R | 24 | | PW | IM | 0-0 | SPARE | D04721J | | 16 | | | | D05573J | | 16 | | | ALL |
| 213Z | | | | IM | 0-0 | SPARE | D04721J | | 18 | | | | D05573J | | 18 | | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1541 | 286T1541 | | | INTERSHELF R2A TO P37 | | | | | | | | | | | |
| 003 | 22 | | PA | 14-0 | 22-21-21 | D04363P | | 15 | | | D05373J | | 15 | | ALL |
| 004 | 22 | | PA | 14-0 | 22-24-21 | D04363P | | 14 | | | D04361J | | 14 | | ALL |
| 005 | 22 | | PA | 14-0 | 22-22-21 | D04363P | | 20 | | | D04361J | | 10 | | ALL |
| 007 | 20 | | PA | 15-0 | 27-61-18 | D04363P | | 2 | | | D05317P | | 7 | | ALL |
| 008 | 20 | | PA | 15-0 | 27-61-18 | D04363P | | 1 | | | D05317P | | 6 | | ALL |
| 009 | 22 | | PA | 15-0 | 27-09-12 | D04363P | | 3 | | | D05317P | | 3 | | ALL |
| 010 | 22 | | PA | 15-0 | SPARE | D04363P | | 4 | | | D05317P | | 4 | | ALL |
| 013 | 22 | | PA | 15-0 | SPARE | D04363P | | 12 | | | D05317P | | 2 | | ALL |
| 014 | 22 | | PA | 14-0 | SPARE | D04363P | | 13 | | | D04361J | | 13 | | ALL |
| 015Y | 22 | | PJ | 14-0 | 27-41-21 | D04363P | | 5 | | | D04361J | | 3 | | ALL |
| 016 | 22 | | PA | 14-0 | 22-22-21 | D04363P | | 30 | | | D04361J | | 5 | | ALL |
| 018 | 24 | | PK | 14-0 | SPARE | D04363P | | 41 | | | D04361J | | 1 | | ALL |
| 020 | 22 | | PA | 14-0 | 27-61-11 | D04363P | | 26 | | | D04361J | | 16 | | ALL |
| 021 | 22 | | PA | 15-0 | 27-09-13 | D04363P | | 29 | | | D05317P | | 1 | | ALL |
| 022 | 22 | | PA | 15-0 | 27-09-13 | D04363P | | 28 | | | D05317P | | 5 | | ALL |
| 023 | 22 | | PA | 14-0 | 27-41-21 | D04363P | | 16 | | | D04361J | | 26 | | ALL |
| 024 | 22 | | PA | 14-0 | 31-31-14 | D04363P | | 44 | | | D05373J | | 4 | | ALL |
| 024Y | 22 | | PJ | 14-0 | 27-41-21 | D04363P | | 27 | | | D04361J | | 27 | | ALL |
| 027 | 22 | | PA | 14-0 | 31-31-18 | D04363P | | 37 | | | D04361J | | 17 | | ALL |
| 028 | 22 | | PA | 14-0 | 31-31-18 | D04363P | | 38 | | | D04361J | | 18 | | ALL |
| 029 | 22 | | PA | 14-0 | 31-31-18 | D04363P | | 39 | | | D04361J | | 19 | | ALL |
| 030 | 22 | | PA | 14-0 | 31-31-18 | D04363P | | 40 | | | D04361J | | 20 | | ALL |
| 031 | 22 | | PA | 14-0 | 22-21-21 | D04363P | | 31 | | | D05373J | | 1 | | ALL |
| 032 | 22 | | PA | 14-0 | SPARE | D04363P | | 32 | | | D05373J | | 2 | | ALL |
| 033 | 22 | | PA | 14-0 | SPARE | D04363P | | 33 | | | D05373J | | 3 | | ALL |
| 034 | 22 | | PA | 14-0 | SPARE | D04363P | | 34 | | | D04361J | | 4 | | ALL |
| 202B | 24 | | PW | IB | 14-0 | 22-21-21 | D04363P | | 11 | | D05373J | | 11 | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 22-21-21 | D04363P | | 10 | | D05373J | | 10 | | ALL |
| 202Z | | | | IB | 0-0 | 22-21-21 | D04363P | | 9 | | D05373J | | 9 | | ALL |
| 203B | 24 | | PL | IC | 14-0 | 22-12-21 | D04363P | | 36 | | D04361J | | 12 | | ALL |
| 203R | 24 | | PL | IC | 0-0 | 22-12-21 | D04363P | | 35 | | D04361J | | 11 | | ALL |
| 206B | 24 | | PW | IF | 14-0 | 22-22-21 | D04363P | | 18 | | D04361J | | 8 | | ALL |
| 206R | 24 | | PW | IF | 0-0 | 22-22-21 | D04363P | | 17 | | D04361J | | 7 | | ALL |
| 206Z | | | | IF | 0-0 | 22-22-21 | D04363P | | 19 | | D04361J | | 9 | | ALL |
| 207B | 22 | | PB | IG | 14-0 | 27-41-21 | D04363P | | 22 | | D04361J | | 22 | | ALL |
| 207R | 22 | | PB | IG | 0-0 | 27-41-21 | D04363P | | 21 | | D04361J | | 21 | | ALL |
| 208B | 24 | | PW | IH | 14-0 | 27-11-22 | D04363P | | 24 | | D04361J | | 24 | | ALL |
| 208R | 24 | | PW | IH | 0-0 | 27-11-22 | D04363P | | 23 | | D04361J | | 23 | | ALL |
| 208Z | | | | IH | 0-0 | 27-11-22 | D04363P | | 25 | | D04361J | | 15 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1540
Page 1
Mar 09/2006



| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1541 | 286T1541 | | | INTERSHELF R2A TO P37 (continued) | | | | | | | | | | | |
| 209B | 24 | PW | II | | 14-0 | SPARE | D04363P | | 7 | | D05373J | | 18 | | ALL |
| 209R | 24 | PW | II | | 0-0 | SPARE | D04363P | | 6 | | D05373J | | 17 | | ALL |
| 209Z | | | II | | 0-0 | SPARE | D04363P | | 8 | | D05373J | | 19 | | ALL |
| 210B | 24 | PL | IJ | | 14-0 | 27-32-21 | D04363P | | 43 | | D04361J | | 6 | | ALL |
| 210R | 24 | PL | IJ | | 0-0 | 27-32-21 | D04363P | | 42 | | D04361J | | 2 | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1561 | 286T1561 | | | INTERSHELF,L,E1-6 TO SHELVES | | | | | | | | | | | |
| 004 | 22 | | PA | | 5-0 | 34-21-11 | D04719J | | 1 | | D04831J | | 32 | | ALL |
| 005 | 22 | | PA | | 5-0 | 34-21-11 | D04719J | | 2 | | D04831J | | 30 | | ALL |
| 006 | 22 | | PA | | 5-0 | 34-21-11 | D04719J | | 3 | | D04831J | | 31 | | ALL |
| 017 | 24 | | PK | | 17-0 | 34-21-11 | D04719J | | 37 | | D04717J | | 17 | | ALL |
| 025 | 24 | | PK | | 5-0 | SPARE | D04719J | | 25 | | D04831J | | 25 | | ALL |
| 026 | 24 | | PK | | 5-0 | SPARE | D04719J | | 26 | | D04831J | | 26 | | ALL |
| 027 | 24 | | PK | | 5-0 | SPARE | D04719J | | 27 | | D04831J | | 27 | | ALL |
| 028 | 24 | | PK | | 5-0 | SPARE | D04719J | | 28 | | D04831J | | 28 | | ALL |
| 029 | 24 | | PK | | 17-0 | SPARE | D04719J | | 29 | | D04717J | | 10 | | ALL |
| 030 | 24 | | PK | | 17-0 | SPARE | D04719J | | 30 | | D04717J | | 11 | | ALL |
| 201B | 24 | | PW | IA | 5-0 | 22-13-11 | D04719J | | 11 | | D04831J | | 11 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 22-13-11 | D04719J | | 10 | | D04831J | | 10 | | ALL |
| 201Z | | | | IA | 0-0 | 22-13-11 | D04719J | | 12 | | D04831J | | 12 | | ALL |
| 202B | 24 | | PW | IB | 5-0 | 22-32-11 | D04719J | | 14 | | D04831J | | 14 | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 22-32-11 | D04719J | | 13 | | D04831J | | 13 | | ALL |
| 202Z | | | | IB | 0-0 | 22-32-11 | D04719J | | 15 | | D04831J | | 15 | | ALL |
| 203B | 24 | | PW | IC | 5-0 | 34-21-11 | D04719J | | 17 | | D04831J | | 17 | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 34-21-11 | D04719J | | 16 | | D04831J | | 16 | | ALL |
| 203Z | | | | IC | 0-0 | 34-21-11 | D04719J | | 18 | | D04831J | | 18 | | ALL |
| 204B | 24 | | PW | ID | 5-0 | 34-22-18 | D04719J | | 20 | | D04831J | | 20 | | ALL |
| 204R | 24 | | PW | ID | 0-0 | 34-22-18 | D04719J | | 19 | | D04831J | | 19 | | ALL |
| 204Z | | | | ID | 0-0 | 34-22-18 | D04719J | | 21 | | D04831J | | 21 | | ALL |
| 205B | 24 | | PW | IE | 17-0 | 34-61-12 | D04719J | | 8 | | D04717J | | 8 | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 34-61-12 | D04719J | | 7 | | D04717J | | 7 | | ALL |
| 205Z | | | | IE | 0-0 | 34-61-12 | D04719J | | 9 | | D04717J | | 9 | | ALL |
| 206B | 24 | | PW | IF | 17-0 | 34-21-11 | D04719J | | 5 | | D04717J | | 5 | | ALL |
| 206R | 24 | | PW | IF | 0-0 | 34-21-11 | D04719J | | 4 | | D04717J | | 4 | | ALL |
| 206Z | | | | IF | 0-0 | 34-21-11 | D04719J | | 6 | | D04717J | | 6 | | ALL |
| 207B | 24 | | PW | IG | 5-0 | SPARE | D04719J | | 23 | | D04831J | | 23 | | ALL |
| 207R | 24 | | PW | IG | 0-0 | SPARE | D04719J | | 22 | | D04831J | | 22 | | ALL |
| 207Z | | | | IG | 0-0 | SPARE | D04719J | | 24 | | D04831J | | 24 | | ALL |
| 208B | 24 | | PW | IH | 17-0 | 34-61-15 | D04719J | | 32 | | D04717J | | 22 | | ALL |
| 208R | 24 | | PW | IH | 0-0 | 34-61-15 | D04719J | | 31 | | D04717J | | 21 | | ALL |
| 208Z | | | | IH | 0-0 | 34-61-15 | D04719J | | 33 | | D04717J | | 23 | | ALL |
| 209B | 24 | | PW | II | 5-0 | 34-22-38 | D04831J | | 2 | | D04719J | | 52 | | ALL |
| 209R | 24 | | PW | II | 0-0 | 34-22-38 | D04831J | | 1 | | D04719J | | 51 | | ALL |
| 209Z | | | | II | 0-0 | 34-22-38 | D04831J | | 3 | | D04719J | | 53 | | ALL |
| 210B | 24 | | PW | IJ | 5-0 | 32-42-11 | D04719J | | 35 | | D04831J | | 35 | | ALL |
| 210R | 24 | | PW | IJ | 0-0 | 32-42-11 | D04719J | | 34 | | D04831J | | 34 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1560
Page 1
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1561 | 286T1561 | | | INTERSHELF,L,E1-6 TO SHELVES (continued) | | | | | | | | | | | |
| 210Z | | | | IJ | 0-0 | 32-42-11 | D04719J | | 36 | | D04831J | | 36 | | ALL |
| 213B | 24 | | PW | IM | 5-0 | 22-21-21 | D04831J | | 39 | | D04719J | | 39 | | ALL |
| 213R | 24 | | PW | IM | 0-0 | 22-21-21 | D04831J | | 38 | | D04719J | | 38 | | ALL |
| 213Z | | | | IM | 0-0 | 22-21-21 | D04831J | | 40 | | D04719J | | 40 | | ALL |
| 214B | 24 | | PW | IN | 5-0 | 34-21-21 | D04831J | | 9 | | D04719J | | 42 | | ALL |
| 214R | 24 | | PW | IN | 0-0 | 34-21-21 | D04831J | | 8 | | D04719J | | 41 | | ALL |
| 214Z | | | | IN | 0-0 | 34-21-21 | D04831J | | 29 | | D04719J | | 43 | | ALL |
| 215B | 24 | | PW | IO | 17-0 | 23-25-13 | D04717J | | 14 | | D04719J | | 45 | | 156-157, 166-199, 277-299 |
| 215R | 24 | | PW | IO | 0-0 | 23-25-13 | D04717J | | 13 | | D04719J | | 44 | | 156-157, 166-199, 277-299 |
| 215Z | | | | IO | 0-0 | 23-25-13 | D04717J | | 12 | | D04719J | | 46 | | 156-157, 166-199, 277-299 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1577 | 286T1577 | | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | |
| 001 | 24 | | PK | | 34-0 | 23-32-13 | D01231 | | 6 | | D02051 | | H | | 150-199 |
| 002 | 24 | | PK | | 34-0 | 23-32-13 | D01231 | | 7 | | D02051 | | E | | 150-199 |
| 003 | 24 | | PK | | 34-0 | 23-32-13 | D01231 | | 8 | | D02051 | | F | | 150-199 |
| 004 | 20 | | PA | | 34-0 | 23-32-13 | D01231 | | 2 | | D02051 | | M | | 150-199 |
| 005 | 20 | | PA | | 34-0 | 23-32-13 | D01231 | | 3 | | D02051 | | G | | 150-199 |
| 006 | 20 | | PA | | 34-0 | 23-32-13 | D01231 | | 5 | | D02051 | | J | | 150-199 |
| 007 | 20 | | PA | | 34-0 | 23-32-11 | D01231 | | 1 | | D02051 | | K | | 150-199 |
| 008 | 20 | | PA | | 34-0 | 23-32-11 | D01231 | | 4 | | D02051 | | L | | 150-199 |
| 01CO | | | | A | 0-0 | 23-32-13 | D01233 | | = C1 | | D02047 | | = C1 | | 150-199 |
| 01CX | | | 5X | A | 34-0 | 23-32-13 | D01233 | | = A1 | | D02047 | | = A1 | | 150-199 |
| W1579 | 286T1579 | | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | |
| 001 | 24 | | PK | | 47-0 | 23-32-13 | D11822 | | 6 | | D02053 | | H | | 150-199 |
| 002 | 24 | | PK | | 47-0 | 23-32-13 | D11822 | | 7 | | D02053 | | E | | 150-199 |
| 003 | 24 | | PK | | 47-0 | 23-32-13 | D11822 | | 8 | | D02053 | | F | | 150-199 |
| 004 | 20 | | PA | | 47-0 | 23-32-13 | D11822 | | 2 | | D02053 | | M | | 150-199 |
| 005 | 20 | | PA | | 47-0 | 23-32-13 | D11822 | | 3 | | D02053 | | G | | 150-199 |
| 006 | 20 | | PA | | 47-0 | 23-32-13 | D11822 | | 5 | | D02053 | | J | | 150-199 |
| 007 | 20 | | PA | | 47-0 | 23-32-11 | D11822 | | 1 | | D02053 | | K | | 150-199 |
| 008 | 20 | | PA | | 47-0 | 23-32-11 | D11822 | | 4 | | D02053 | | L | | 150-199 |
| 01CO | | | | A | 0-0 | 23-32-13 | D11824 | | = C1 | | D02049 | | = C1 | | 150-199 |
| 01CX | | | 5X | A | 47-0 | 23-32-13 | D11824 | | = A1 | | D02049 | | = A1 | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W1570
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|----------|--------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1581 | 286T1581 | | | INTERSHELF C E1-6 TO SHELF | | | | | | | | | | | | |
| 001 | 24 | | PK | 10-0 | SPARE | D05153J | | 1 | | | D05151J | | 1 | | 050-099 | |
| 002 | 24 | | PK | 10-0 | SPARE | D05153J | | 2 | | | D05151J | | 2 | | 050-099 | |
| 003 | 24 | | PK | 10-0 | SPARE | D05153J | | 3 | | | D05151J | | 3 | | 050-099 | |
| 004 | 24 | | PK | 10-0 | SPARE | D05153J | | 4 | | | D05151J | | 4 | | 050-099 | |
| 005 | 24 | | PK | 10-0 | SPARE | D05153J | | 5 | | | D05151J | | 5 | | 050-099 | |
| 005 | 24 | | PK | 9-0 | SPARE | D05153J | | 5 | | | D05151J | | 5 | | 150-199, 275-299 | |
| 012 | 24 | | PK | 10-0 | SPARE | D05153J | | 12 | | | D05151J | | 12 | | 050-099 | |
| 012 | 24 | | PK | 9-0 | SPARE | D05153J | | 12 | | | D05151J | | 12 | | 150-199, 275-299 | |
| 013 | 24 | | PK | 10-0 | SPARE | D05153J | | 13 | | | D05151J | | 13 | | 050-099 | |
| 016 | 24 | | PK | 10-0 | SPARE | D05153J | | 16 | | | D05151J | | 16 | | 050-099 | |
| 017 | 22 | | PA | 10-0 | SPARE | D05153J | | 17 | | | D05151J | | 17 | | 050-099 | |
| 201B | 24 | | PW | IA | 10-0 | 34-61-12 | D05153J | 7 | | | D05151J | | 7 | | 050-099 | |
| 201B | 24 | | PW | IA | 9-0 | 34-61-12 | D05153J | 7 | | | D05151J | | 7 | | 150-199, 275-299 | |
| 201R | 24 | | PW | IA | 0-0 | 34-61-12 | D05153J | 6 | | | D05151J | | 6 | | ALL | |
| 201Z | | | | IA | 0-0 | 34-61-12 | D05153J | 8 | | | D05151J | | 8 | | ALL | |
| 202B | 24 | | PW | IB | 10-0 | SPARE | D05153J | 10 | | | D05151J | | 10 | | 050-099 | |
| 202B | 24 | | PW | IB | 9-0 | SPARE | D05153J | 10 | | | D05151J | | 10 | | 150-199, 275-299 | |
| 202R | 24 | | PW | IB | 0-0 | SPARE | D05153J | 9 | | | D05151J | | 9 | | ALL | |
| 202Z | | | | IB | 0-0 | SPARE | D05153J | 11 | | | D05151J | | 11 | | ALL | |
| 235B | 24 | | PW | JJ | 10-0 | 31-35-13 | D05153J | 14 | | | D05151J | | 14 | | 050-099 | |
| 235B | 24 | | PW | JJ | 9-0 | 31-35-13 | D05153J | 14 | | | D05151J | | 14 | | 150-199, 275-299 | |
| 235R | 24 | | PW | JJ | 0-0 | 31-35-13 | D05153J | 15 | | | D05151J | | 15 | | ALL | |
| 235Z | | | | JJ | 0-0 | 31-35-13 | D05153J | 18 | | | D05151J | | 18 | | ALL | |
| W1589 | 286T1589 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | |
| 001 | 24 | | PK | 19-0 | 23-32-13 | D02229 | | 6 | | | D02041 | | H | | 150-199 | |
| 002 | 24 | | PK | 19-0 | 23-32-13 | D02229 | | 7 | | | D02041 | | E | | 150-199 | |
| 003 | 24 | | PK | 19-0 | 23-32-13 | D02229 | | 8 | | | D02041 | | F | | 150-199 | |
| 004 | 20 | | PA | 19-0 | 23-32-13 | D02229 | | 2 | | | D02041 | | M | | 150-199 | |
| 005 | 20 | | PA | 19-0 | 23-32-13 | D02229 | | 3 | | | D02041 | | G | | 150-199 | |
| 006 | 20 | | PA | 19-0 | 23-32-13 | D02229 | | 5 | | | D02041 | | J | | 150-199 | |
| 007 | 20 | | PA | 19-0 | 23-32-11 | D02229 | | 1 | | | D02041 | | K | | 150-199 | |
| 008 | 20 | | PA | 19-0 | 23-32-11 | D02229 | | 4 | | | D02041 | | L | | 150-199 | |
| 01CO | | | | A | 0-0 | 23-32-13 | D02227 | = C1 | | | D02037 | | = C1 | | 150-199 | |
| 01CX | | | | 5X | A | 19-0 | 23-32-13 | D02227 | = A1 | | D02037 | | = A1 | | 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W1580

Page 1 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|-------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1591 | 286T1591 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 24 | | PK | | 34-0 | 23-32-13 | D02225 | | 6 | | D02039 | | H | | 050-099 |
| 001 | 24 | | PK | | 31-0 | 23-32-13 | D02225 | | 6 | | D02039 | | H | | 150-199 |
| 002 | 24 | | PK | | 34-0 | 23-32-13 | D02225 | | 7 | | D02039 | | E | | 050-099 |
| 002 | 24 | | PK | | 31-0 | 23-32-13 | D02225 | | 7 | | D02039 | | E | | 150-199 |
| 003 | 24 | | PK | | 34-0 | 23-32-13 | D02225 | | 8 | | D02039 | | F | | 050-099 |
| 003 | 24 | | PK | | 31-0 | 23-32-13 | D02225 | | 8 | | D02039 | | F | | 150-199 |
| 004 | 20 | | PA | | 34-0 | 23-32-13 | D02225 | | 2 | | D02039 | | M | | 050-099 |
| 004 | 20 | | PA | | 31-0 | 23-32-13 | D02225 | | 2 | | D02039 | | M | | 150-199 |
| 005 | 20 | | PA | | 34-0 | 23-32-13 | D02225 | | 3 | | D02039 | | G | | 050-099 |
| 005 | 20 | | PA | | 31-0 | 23-32-13 | D02225 | | 3 | | D02039 | | G | | 150-199 |
| 006 | 20 | | PA | | 34-0 | 23-32-13 | D02225 | | 5 | | D02039 | | J | | 050-099 |
| 006 | 20 | | PA | | 31-0 | 23-32-13 | D02225 | | 5 | | D02039 | | J | | 150-199 |
| 007 | 20 | | PA | | 34-0 | 23-32-11 | D02225 | | 1 | | D02039 | | K | | 050-099 |
| 007 | 20 | | PA | | 31-0 | 23-32-11 | D02225 | | 1 | | D02039 | | K | | 150-199 |
| 008 | 20 | | PA | | 34-0 | 23-32-11 | D02225 | | 4 | | D02039 | | L | | 050-099 |
| 008 | 20 | | PA | | 31-0 | 23-32-11 | D02225 | | 4 | | D02039 | | L | | 150-199 |
| 01CO | | | | A | 0-0 | 23-32-13 | D02035 | | = C1 | | D02223 | | = C1 | | 050-099, 150-199 |
| 01CX | | 5X | | A | 34-0 | 23-32-13 | D02035 | | = A1 | | D02223 | | = A1 | | 050-099 |
| 01CX | | 5X | | A | 31-0 | 23-32-13 | D02035 | | = A1 | | D02223 | | = A1 | | 150-199 |
| W1597 | 286T1597 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 24 | | PK | | 18-0 | 23-32-13 | D02773 | | | | D06191J | | 6 | | 050-099 |
| 002 | 24 | | PK | | 18-0 | 23-32-13 | D02773 | | | | D06191J | | 7 | | 050-099 |
| 003 | 24 | | PK | | 18-0 | 23-32-13 | D02773 | | | | D06191J | | 8 | | 050-099 |
| 004 | 20 | | PA | | 18-0 | 23-32-13 | D02773 | | | | D06191J | | 2 | | 050-099 |
| 005 | 20 | | PA | | 18-0 | 23-32-13 | D02773 | | | | D06191J | | 3 | | 050-099 |
| 006 | 20 | | PA | | 18-0 | 23-32-13 | D02773 | | | | D06191J | | 5 | | 050-099 |
| 007 | 20 | | PA | | 18-0 | 23-32-11 | D02773 | | | | D06191J | | 1 | | 050-099 |
| 008 | 20 | | PA | | 18-0 | 23-32-11 | D02773 | | | | D06191J | | 4 | | 050-099 |
| 01CO | | | | A | 0-0 | 23-32-13 | D02775 | | = C1 | | D06191J | | = C15 | | 050-099 |
| 01CX | | 5X | | A | 18-0 | 23-32-13 | D02775 | | = A1 | | D06191J | | = 15 | | 050-099 |
| W1599 | 286T1599 | | | EFIS INTERSHELF N,E1-2 TO E1-4 | | | | | | | | | | | |
| 201W | 24 | | BV | IA | 4-0 | 34-22-35 | D04371J | | 2 | | D04387J | | 2 | | ALL |
| 201WN | 24 | | BV | IA | 0-0 | 34-22-35 | D04371J | | 1 | | D04387J | | 1 | | ALL |
| 201Z | | | | IA | 0-0 | 34-22-35 | D04371J | | 3 | | D04387J | | 3 | | ALL |
| 202W | 24 | | BV | IB | 4-0 | 34-22-35 | D04371J | | 5 | | D04387J | | 5 | | ALL |
| 202WN | 24 | | BV | IB | 0-0 | 34-22-35 | D04371J | | 4 | | D04387J | | 4 | | ALL |
| 202Z | | | | IB | 0-0 | 34-22-35 | D04371J | | 6 | | D04387J | | 6 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1590

Page 1

Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1599 | 286T1599 | | | EFIS INTERSHELF N,E1-2 TO E1-4 (continued) | | | | | | | | | | | | |
| 203W | 24 | BV | IC | 4-0 | 34-22-35 | D04371J | | 8 | | | D04387J | | 8 | | ALL | |
| 203WN | 24 | BV | IC | 0-0 | 34-22-35 | D04371J | | 7 | | | D04387J | | 7 | | ALL | |
| 203Z | | | IC | 0-0 | 34-22-35 | D04371J | | 9 | | | D04387J | | 9 | | ALL | |
| 204W | 24 | BV | ID | 4-0 | 34-22-35 | D04371J | | 11 | | | D04387J | | 11 | | ALL | |
| 204WN | 24 | BV | ID | 0-0 | 34-22-35 | D04371J | | 10 | | | D04387J | | 10 | | ALL | |
| 204Z | | | ID | 0-0 | 34-22-35 | D04371J | | 12 | | | D04387J | | 12 | | ALL | |
| 205W | 24 | BV | IE | 4-0 | 34-22-35 | D04371J | | 14 | | | D04387J | | 14 | | ALL | |
| 205WN | 24 | BV | IE | 0-0 | 34-22-35 | D04371J | | 13 | | | D04387J | | 13 | | ALL | |
| 205Z | | | IE | 0-0 | 34-22-35 | D04371J | | 15 | | | D04387J | | 15 | | ALL | |
| 206W | 24 | BV | IF | 4-0 | 34-22-35 | D04371J | | 17 | | | D04387J | | 17 | | ALL | |
| 206WN | 24 | BV | IF | 0-0 | 34-22-35 | D04371J | | 16 | | | D04387J | | 16 | | ALL | |
| 206Z | | | IF | 0-0 | 34-22-35 | D04371J | | 18 | | | D04387J | | 18 | | ALL | |
| 207W | 24 | BV | IG | 4-0 | 34-22-35 | D04371J | | 20 | | | D04387J | | 20 | | ALL | |
| 207WN | 24 | BV | IG | 0-0 | 34-22-35 | D04371J | | 19 | | | D04387J | | 19 | | ALL | |
| 207Z | | | IG | 0-0 | 34-22-35 | D04371J | | 21 | | | D04387J | | 21 | | ALL | |
| 208W | 24 | BV | IH | 4-0 | 34-22-35 | D04371J | | 23 | | | D04387J | | 23 | | ALL | |
| 208WN | 24 | BV | IH | 0-0 | 34-22-35 | D04371J | | 22 | | | D04387J | | 22 | | ALL | |
| 208Z | | | IH | 0-0 | 34-22-35 | D04371J | | 24 | | | D04387J | | 24 | | ALL | |
| 209W | 24 | BV | II | 4-0 | 34-22-35 | D04371J | | 26 | | | D04387J | | 26 | | ALL | |
| 209WN | 24 | BV | II | 0-0 | 34-22-35 | D04371J | | 25 | | | D04387J | | 25 | | ALL | |
| 209Z | | | II | 0-0 | 34-22-35 | D04371J | | 27 | | | D04387J | | 27 | | ALL | |
| 210W | 24 | BV | IJ | 4-0 | 34-22-35 | D04371J | | 29 | | | D04387J | | 29 | | ALL | |
| 210WN | 24 | BV | IJ | 0-0 | 34-22-35 | D04371J | | 28 | | | D04387J | | 28 | | ALL | |
| 210Z | | | IJ | 0-0 | 34-22-35 | D04371J | | 30 | | | D04387J | | 30 | | ALL | |
| 211W | 24 | BV | IK | 4-0 | 34-22-35 | D04371J | | 32 | | | D04387J | | 32 | | ALL | |
| 211WN | 24 | BV | IK | 0-0 | 34-22-35 | D04371J | | 31 | | | D04387J | | 31 | | ALL | |
| 211Z | | | IK | 0-0 | 34-22-35 | D04371J | | 33 | | | D04387J | | 33 | | ALL | |
| 212W | 24 | BV | IL | 4-0 | 34-22-35 | D04371J | | 35 | | | D04387J | | 35 | | ALL | |
| 212WN | 24 | BV | IL | 0-0 | 34-22-35 | D04371J | | 34 | | | D04387J | | 34 | | ALL | |
| 212Z | | | IL | 0-0 | 34-22-35 | D04371J | | 36 | | | D04387J | | 36 | | ALL | |
| 213W | 24 | BV | IM | 4-0 | 34-22-35 | D04371J | | 38 | | | D04387J | | 38 | | ALL | |
| 213WN | 24 | BV | IM | 0-0 | 34-22-35 | D04371J | | 37 | | | D04387J | | 37 | | ALL | |
| 213Z | | | IM | 0-0 | 34-22-35 | D04371J | | 39 | | | D04387J | | 39 | | ALL | |
| 214W | 24 | BV | IN | 4-0 | 34-22-35 | D04371J | | 41 | | | D04387J | | 41 | | ALL | |
| 214WN | 24 | BV | IN | 0-0 | 34-22-35 | D04371J | | 40 | | | D04387J | | 40 | | ALL | |
| 214Z | | | IN | 0-0 | 34-22-35 | D04371J | | 42 | | | D04387J | | 42 | | ALL | |
| 215W | 24 | BV | IO | 4-0 | 34-22-35 | D04371J | | 44 | | | D04387J | | 44 | | ALL | |
| 215WN | 24 | BV | IO | 0-0 | 34-22-35 | D04371J | | 43 | | | D04387J | | 43 | | ALL | |
| 215Z | | | IO | 0-0 | 34-22-35 | D04371J | | 45 | | | D04387J | | 45 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1590

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1599 | 286T1599 | | | | EFIS INTERSHELF N,E1-2 TO E1-4 (continued) | | | | | | | | | | |
| 216W | 24 | BV | IP | 4-0 | 34-22-35 | D04371J | | 47 | | D04387J | | 47 | | ALL | |
| 216WN | 24 | BV | IP | 0-0 | 34-22-35 | D04371J | | 46 | | D04387J | | 46 | | ALL | |
| 216Z | | | IP | 0-0 | 34-22-35 | D04371J | | 48 | | D04387J | | 48 | | ALL | |
| 217W | 24 | BV | IQ | 4-0 | 34-22-35 | D04371J | | 50 | | D04387J | | 50 | | ALL | |
| 217WN | 24 | BV | IQ | 0-0 | 34-22-35 | D04371J | | 49 | | D04387J | | 49 | | ALL | |
| 217Z | | | IQ | 0-0 | 34-22-35 | D04371J | | 51 | | D04387J | | 51 | | ALL | |
| 218W | 24 | BV | IR | 4-0 | 34-22-35 | D04371J | | 53 | | D04387J | | 53 | | ALL | |
| 218WN | 24 | BV | IR | 0-0 | 34-22-35 | D04371J | | 52 | | D04387J | | 52 | | ALL | |
| 218Z | | | IR | 0-0 | 34-22-35 | D04371J | | 54 | | D04387J | | 54 | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W1590
Page 3 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1601 | 286T1601 | | | INTERSHELF E1-1 TO E2-1 SHELF | | | | | | | | | | | |
| 001 | 22 | | PA | 7-3 | 22-21-21 | D05413P | | | 1 | | D05547P | | | 1 | ALL |
| 002 | 22 | | PA | 7-3 | 22-22-11 | D05413P | | | 2 | | D05547P | | | 2 | ALL |
| 003 | 22 | | PA | 7-3 | 22-24-11 | D05413P | | | 3 | | D05547P | | | 3 | ALL |
| 004 | 22 | | PA | 7-3 | 27-41-21 | D05413P | | | 4 | | D05547P | | | 4 | 150-154 |
| 005 | 22 | | PA | 7-3 | 22-24-11 | D05413P | | | 5 | | D05547P | | | 5 | ALL |
| 006 | 22 | | PA | 7-3 | 22-24-11 | D05413P | | | 6 | | D05547P | | | 6 | ALL |
| 007 | 22 | | PA | 7-3 | 27-09-12 | D05413P | | | 7 | | D05547P | | | 7 | ALL |
| 008 | 22 | | PA | 7-3 | 27-09-13 | D05413P | | | 8 | | D05547P | | | 8 | ALL |
| 009 | 22 | | PA | 7-3 | 27-09-13 | D05413P | | | 9 | | D05547P | | | 9 | ALL |
| 010 | 22 | | PA | 7-3 | 27-11-22 | D05413P | | | 10 | | D05547P | | | 10 | ALL |
| 011 | 22 | | PA | 7-3 | 27-11-22 | D05413P | | | 11 | | D05547P | | | 11 | ALL |
| 012 | 22 | | PA | 7-3 | 27-21-12 | D05413P | | | 12 | | D05547P | | | 12 | ALL |
| 013 | 22 | | PA | 7-3 | 27-21-22 | D05413P | | | 13 | | D05547P | | | 13 | ALL |
| 022 | 22 | | PA | 7-3 | 27-21-22 | D05413P | | | 22 | | D05547P | | | 22 | ALL |
| 023 | 22 | | PA | 7-3 | 27-21-22 | D05413P | | | 23 | | D05547P | | | 23 | ALL |
| 024 | 22 | | PA | 7-3 | 27-21-22 | D05413P | | | 24 | | D05547P | | | 24 | ALL |
| 025 | 22 | | PA | 7-3 | 27-41-11 | D05413P | | | 25 | | D05547P | | | 25 | ALL |
| 026 | 22 | | PA | 7-3 | 27-41-11 | D05413P | | | 26 | | D05547P | | | 26 | ALL |
| 027 | 22 | | PA | 7-3 | 27-41-11 | D05413P | | | 27 | | D05547P | | | 27 | ALL |
| 028 | 22 | | PA | 7-3 | 27-41-11 | D05413P | | | 28 | | D05547P | | | 28 | ALL |
| 029 | 22 | | PA | 7-3 | 27-61-11 | D05413P | | | 29 | | D05547P | | | 29 | ALL |
| 030 | 22 | | PA | 7-3 | SPARE | D05413P | | | 30 | | D05547P | | | 30 | ALL |
| 031 | 22 | | PA | 7-3 | SPARE | D05413P | | | 31 | | D05547P | | | 31 | ALL |
| 032 | 22 | | PA | 7-3 | SPARE | D05413P | | | 32 | | D05547P | | | 32 | ALL |
| 033 | 22 | | PA | 7-3 | SPARE | D05413P | | | 33 | | D05547P | | | 33 | ALL |
| 041 | 22 | | PA | 13-0 | SPARE | D05391J | | | 1 | | D05547P | | | 36 | ALL |
| 042 | 22 | | PA | 13-0 | SPARE | D05391J | | | 2 | | D05547P | | | 37 | ALL |
| 201B | 24 | | PW | IA | 13-0 | 22-21-21 | D05391J | | 6 | | D05547P | | | 16 | ALL |
| 201R | 24 | | PW | IA | 0-0 | 22-21-21 | D05391J | | 5 | | D05547P | | | 15 | ALL |
| 201Z | | | | IA | 0-0 | 22-21-21 | D05391J | | 7 | | D05547P | | | 17 | ALL |
| 202B | 24 | | PW | IB | 13-0 | 27-11-22 | D05391J | | 9 | | D05547P | | | 19 | ALL |
| 202R | 24 | | PW | IB | 0-0 | 27-11-22 | D05391J | | 8 | | D05547P | | | 18 | ALL |
| 202Z | | | | IB | 0-0 | 27-11-22 | D05391J | | 10 | | D05547P | | | 20 | ALL |
| 203B | 22 | | PB | IC | 7-3 | 27-21-22 | D05413P | | 35 | | D05547P | | | 35 | ALL |
| 203R | 22 | | PB | IC | 0-0 | 27-21-22 | D05413P | | 34 | | D05547P | | | 34 | ALL |
| 204B | 24 | | PW | ID | 13-0 | SPARE | D05391J | | 11 | | D05547P | | | 39 | ALL |
| 204R | 24 | | PW | ID | 0-0 | SPARE | D05391J | | 3 | | D05547P | | | 38 | ALL |
| 204Z | | | | ID | 0-0 | SPARE | D05391J | | 12 | | D05547P | | | 40 | ALL |

WIRE LIST

D280T132

91-21-11

Section W1600

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1603 | 286T1603 | | | INTERSHELF L,E1-2,E1-4,E2-3 | | | | | | | | | | | |
| 001 | 24 | | PK | 4-0 | 34-22-37 | D04923J | | 1 | | | D05585J | | 1 | | 050-099 |
| 001 | 24 | | PK | 4-0 | SPARE | D04923J | | 1 | | | D05585J | | 1 | | 150-199, 275-299 |
| 002 | 24 | | PK | 4-0 | 34-22-37 | D04923J | | 2 | | | D05585J | | 2 | | ALL |
| 003 | 24 | | PK | 4-0 | 34-22-37 | D04923J | | 3 | | | D05585J | | 3 | | ALL |
| 004 | 24 | | PK | 4-0 | 34-22-37 | D04923J | | 4 | | | D05585J | | 4 | | ALL |
| 005 | 24 | | PK | 4-0 | SPARE | D04923J | | 5 | | | D05585J | | 5 | | ALL |
| 006 | 24 | | PK | 14-0 | 31-31-13 | D04923J | | 21 | | | D05229J | | 1 | | ALL |
| 007 | 24 | | PK | 14-0 | SPARE | D04923J | | 22 | | | D05229J | | 2 | | 050-099, 150-199 |
| 008 | 24 | | PK | 14-0 | 31-31-13 | D04923J | | 23 | | | D05229J | | 3 | | ALL |
| 009 | 24 | | PK | 14-0 | 31-31-13 | D04923J | | 24 | | | D05229J | | 4 | | ALL |
| 010 | 24 | | PK | 14-0 | 31-31-13 | D04923J | | 25 | | | D05229J | | 5 | | ALL |
| 011 | 24 | | PK | 14-0 | 31-31-13 | D04923J | | 26 | | | D05229J | | 6 | | ALL |
| 012 | 24 | | PK | 14-0 | 31-31-13 | D04923J | | 27 | | | D05229J | | 7 | | ALL |
| 013 | 24 | | PK | 14-0 | 31-31-13 | D04923J | | 28 | | | D05229J | | 8 | | ALL |
| 014 | 24 | | PK | 14-0 | 31-31-13 | D04923J | | 29 | | | D05229J | | 9 | | ALL |
| 015 | 24 | | PK | 14-0 | 31-31-22 | D05223J | | 11 | | | D05229J | | 10 | | ALL |
| 020 | 22 | | PA | 4-0 | SPARE | D04923J | | 41 | | | D05585J | | 27 | | ALL |
| 021 | 22 | | PA | 4-0 | SPARE | D05585J | | 37 | | | D04923J | | 39 | | 050-099 |
| 021 | 22 | | PA | 4-0 | SPARE | D04923J | | 39 | | | D05585J | | 37 | | 150-199, 275-299 |
| 023 | 24 | | PK | 4-0 | 22-41-11 | D04923J | | 50 | | | D05585J | | 38 | | ALL |
| 030 | 22 | | PA | 14-0 | SPARE | D04923J | | 42 | | | D05229J | | 30 | | 150-199, 275-299 |
| 034 | 24 | | PK | 14-0 | 31-31-21 | D04923J | | 48 | | | D05229J | | 28 | | 050-099 |
| 034 | 24 | | PK | 15-0 | 31-31-21 | D05229J | | 28 | | | D04923J | | 48 | | 150-199, 275-299 |
| 035 | 24 | | PK | 14-0 | 31-31-21 | D04923J | | 49 | | | D05229J | | 29 | | 050-099 |
| 035 | 24 | | PK | 15-0 | 31-31-21 | D05229J | | 29 | | | D04923J | | 49 | | 150-199, 275-299 |
| 037 | 24 | | PK | 4-0 | 34-22-38 | D05585J | | 42 | | | D05223J | | 10 | | ALL |
| 038 | 24 | | PK | 14-0 | 34-61-25 | D04923J | | 12 | | | D05229J | | 18 | | ALL |
| 043 | 24 | | PK | 14-0 | 31-31-19 | D04923J | | 43 | | | D05229J | | 24 | | 050-099 |
| 043 | 24 | | PK | 15-0 | 31-31-19 | D05229J | | 24 | | | D04923J | | 43 | | 150-199, 275-299 |
| 060 | 22 | | PA | 2-10 | 34-12-61 | D03691J | | 1 | | | D03129 | | 1 | | ALL |
| 061 | 22 | | PA | 2-10 | 34-12-61 | D03691J | | 2 | | | D03129 | | 2 | | ALL |
| 062 | 22 | | PA | 2-10 | 34-12-61 | D03691J | | 5 | | | D03129 | | 5 | | ALL |
| 063 | 22 | | PA | 2-10 | 34-12-61 | D03691J | | 6 | | | D03129 | | 6 | | ALL |
| 064 | 20 | | PA | 1-4 | 34-12-61 | GD07181 | | D.. | E | | D03129 | | 7 | | ALL |
| 065 | 24 | | PK | 16-6 | 34-12-61 | D05229J | | 11 | | | D03129 | | 8 | | 050-099, 152 |
| 065 | 24 | | PK | 16-6 | 34-12-61 | D05229J | | 12 | | | D03129 | | 8 | | 150-151, 153-199, 275-299 |
| 066 | 24 | | PK | 16-6 | 34-12-61 | D05229J | | 12 | | | D03129 | | 9 | | 050-099, 152 |

WIRE LIST

D280T132

91-21-11

Section W1600

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|---------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1603 | 286T1603 | | | INTERSHELF L,E1-2,E1-4,E2-3 (continued) | | | | | | | | | | | | |
| 066 | 24 | | PK | 16-6 | 34-12-61 | D05229J | | 13 | | | | D03129 | 9 | | 150-151, 153-199, 275-299 | |
| 067 | 24 | | PK | 2-10 | 34-12-61 | D03691J | | 10 | | | | D03129 | 10 | | ALL | |
| 068 | 24 | | PK | 2-10 | 34-12-61 | D03691J | | 11 | | | | D03129 | 11 | | ALL | |
| 069 | 24 | | PK | 16-6 | 34-12-61 | D05229J | | 13 | | | | D03129 | 12 | | 050-099, 152 | |
| 069 | 24 | | PK | 16-6 | 34-12-61 | D05229J | | 14 | | | | D03129 | 12 | | 150-151, 153-199, 275-299 | |
| 101 | 22 | | PA | 14-0 | 31-31-22 | D05223J | | 6 | | | | D05229J | 34 | | ALL | |
| 201B | 24 | | PW IA | 4-0 | 34-22-39 | D04923J | | 7 | | | | D05585J | 7 | | ALL | |
| 201R | 24 | | PW IA | 0-0 | 34-22-39 | D04923J | | 6 | | | | D05585J | 6 | | ALL | |
| 201Z | | | IA | 0-0 | 34-22-39 | D04923J | | 8 | | | | D05585J | 8 | | ALL | |
| 202B | 24 | | PW IB | 4-0 | 34-22-39 | D04923J | | 10 | | | | D05585J | 10 | | ALL | |
| 202R | 24 | | PW IB | 0-0 | 34-22-39 | D04923J | | 9 | | | | D05585J | 9 | | ALL | |
| 202Z | | | IB | 0-0 | 34-22-39 | D04923J | | 11 | | | | D05585J | 11 | | ALL | |
| 204B | 24 | | PW ID | 4-0 | 34-22-35 | D04923J | | 16 | | | | D05585J | 16 | | ALL | |
| 204R | 24 | | PW ID | 0-0 | 34-22-35 | D04923J | | 15 | | | | D05585J | 15 | | ALL | |
| 204Z | | | ID | 0-0 | 34-22-35 | D04923J | | 17 | | | | D05585J | 17 | | ALL | |
| 205W | 24 | | 7K IE | 4-0 | 34-43-11 | D04923J | | 18 | | | | D05585J | 18 | | ALL | |
| 205WB | 24 | | 7K IE | 0-0 | 34-43-11 | D04923J | | 19 | | | | D05585J | 19 | | ALL | |
| 205Z | | | IE | 0-0 | 34-43-11 | D04923J | | 20 | | | | D05585J | 20 | | ALL | |
| 209B | 24 | | PW II | 4-0 | 34-22-13 | D04923J | | 45 | | | | D05585J | 32 | | ALL | |
| 209R | 24 | | PW II | 0-0 | 34-22-13 | D04923J | | 44 | | | | D05585J | 31 | | ALL | |
| 209Z | | | II | 0-0 | 34-22-13 | D04923J | | 46 | | | | D05585J | 33 | | ALL | |
| 210B | 24 | | PW IJ | 4-0 | 22-41-12 | D04923J | | 52 | | | | D05585J | 40 | | ALL | |
| 210R | 24 | | PW IJ | 0-0 | 22-41-12 | D04923J | | 51 | | | | D05585J | 39 | | ALL | |
| 210Z | | | IJ | 0-0 | 22-41-12 | D04923J | | 53 | | | | D05585J | 41 | | ALL | |
| 214B | 24 | | PW IN | 4-0 | 34-22-13 | D05585J | | 22 | | | | D04923J | 31 | | ALL | |
| 214R | 24 | | PW IN | 0-0 | 34-22-13 | D05585J | | 21 | | | | D04923J | 30 | | ALL | |
| 214Z | | | IN | 0-0 | 34-22-13 | D05585J | | 23 | | | | D04923J | 32 | | ALL | |
| 215B | 24 | | PW IO | 4-0 | 34-22-13 | D05585J | | 29 | | | | D04923J | 34 | | ALL | |
| 215R | 24 | | PW IO | 0-0 | 34-22-13 | D05585J | | 28 | | | | D04923J | 33 | | ALL | |
| 215Z | | | IO | 0-0 | 34-22-13 | D05585J | | 30 | | | | D04923J | 35 | | ALL | |
| 216B | 22 | | PR IP | 14-0 | 31-31-22 | D05223J | | 8 | | | | D05229J | 36 | | ALL | |
| 216R | 22 | | PR IP | 0-0 | 31-31-22 | D05223J | | 7 | | | | D05229J | 35 | | ALL | |
| 216Z | | | IP | 0-0 | 31-31-22 | D05223J | | 9 | | | | D05229J | 37 | | ALL | |
| 217B | 24 | | PW IQ | 14-0 | 31-31-20 | D04923J | | 54 | | | | D05229J | 26 | | ALL | |
| 217R | 24 | | PW IQ | 0-0 | 31-31-20 | D04923J | | 55 | | | | D05229J | 25 | | ALL | |
| 217Z | | | IQ | 0-0 | 31-31-20 | D04923J | | 47 | | | | D05229J | 27 | | ALL | |
| 218B | 24 | | PW IR | 14-0 | 34-61-24 | D04923J | | 38 | | | | D05229J | 20 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1600

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|--|----|------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1603 | 286T1603 | INTERSHELF L,E1-2,E1-4,E2-3 (continued) | | | | | | | | | | | | | | | |
| 218R | 24 | PW | IR | 0-0 | 34-61-24 | D04923J | | 37 | | | | | D05229J | 19 | | | ALL |
| 218Z | | | IR | 0-0 | 34-61-24 | D04923J | | 40 | | | | | D05229J | 21 | | | ALL |
| 219B | 24 | PW | IS | 4-0 | 34-22-38 | D05585J | | 25 | | | | | D05223J | 16 | | | ALL |
| 219R | 24 | PW | IS | 0-0 | 34-22-38 | D05585J | | 24 | | | | | D05223J | 15 | | | ALL |
| 219Z | | | IS | 0-0 | 34-22-38 | D05585J | | 26 | | | | | D05223J | 17 | | | ALL |
| 220B | 24 | PW | IT | 4-0 | 34-22-38 | D05585J | | 13 | | | | | D05223J | 13 | | | ALL |
| 220R | 24 | PW | IT | 0-0 | 34-22-38 | D05585J | | 12 | | | | | D05223J | 12 | | | ALL |
| 220Z | | | IT | 0-0 | 34-22-38 | D05585J | | 14 | | | | | D05223J | 14 | | | ALL |
| 230 | 20 | PA | | 1-1 | 34-12-61 | GD07179 | | S.. | E | | | | D03129 | REF | | JE | ALL |
| 230B | 24 | PW | JE | 2-10 | 34-12-61 | D03691J | | 16 | | | | | D03129 | 34 | | | ALL |
| 230R | 24 | PW | JE | 0-0 | 34-12-61 | D03691J | | 17 | | | | | D03129 | 28 | | | ALL |
| 230Z | | | JE | 0-0 | 34-12-61 | D03691J | | 18 | | | | | D03129 | REF | | JE | ALL |
| 231 | 20 | PA | | 1-1 | 34-12-61 | GD07179 | | S.. | E | | | | D03129 | REF | | JF | ALL |
| 231B | 24 | PW | JF | 2-10 | 34-12-61 | D03691J | | 19 | | | | | D03129 | 35 | | | ALL |
| 231R | 24 | PW | JF | 0-0 | 34-12-61 | D03691J | | 20 | | | | | D03129 | 29 | | | ALL |
| 231Z | | | JF | 0-0 | 34-12-61 | D03691J | | 21 | | | | | D03129 | REF | | JF | ALL |
| 232 | 20 | PA | | 1-1 | 34-12-61 | GD07179 | | S.. | E | | | | D03129 | REF | | JG | ALL |
| 232B | 24 | PW | JG | 16-6 | 34-12-61 | D05229J | | 14 | | | | | D03129 | 36 | | | 050-099, 152 |
| 232B | 24 | PW | JG | 16-6 | 34-12-61 | D05229J | | 15 | | | | | D03129 | 36 | | | 150-151, 153-199, 275-299 |
| 232R | 24 | PW | JG | 0-0 | 34-12-61 | D05229J | | 15 | | | | | D03129 | 30 | | | 050-099, 152 |
| 232R | 24 | PW | JG | 0-0 | 34-12-61 | D05229J | | 16 | | | | | D03129 | 30 | | | 150-151, 153-199, 275-299 |
| 232Z | | | JG | 0-0 | 34-12-61 | D05229J | | 16 | | | | | D03129 | REF | | JG | 050-099, 152 |
| 232Z | | | JG | 0-0 | 34-12-61 | D05229J | | 17 | | | | | D03129 | REF | | JG | 150-151, 153-199, 275-299 |
| W1605 | 286T1605 | INTERSHELF L E1-3,E1-5,E2-3 DELTA | | | | | | | | | | | | | | | |
| 001 | 24 | PK | | 3-0 | 22-14-11 | D04855J | | 16 | | | | | D04853J | 6 | | | ALL |
| 002 | 24 | PK | | 3-0 | 22-14-11 | D04855J | | 18 | | | | | D04853J | 8 | | | ALL |
| 003 | 24 | PK | | 3-0 | 22-14-11 | D04855J | | 19 | | | | | D04853J | 9 | | | ALL |
| 004 | 22 | PA | | 3-0 | 22-14-21 | D04855J | | 20 | | | | | D04853J | 10 | | | ALL |
| 005 | 24 | PK | | 3-0 | 22-14-11 | D04855J | | 21 | | | | | D04853J | 11 | | | ALL |
| 006 | 24 | PK | | 3-0 | 22-15-12 | D04855J | | 12 | | | | | D04853J | 2 | | | ALL |
| 007 | 24 | PK | | 3-0 | 34-46-12 | D04853J | | 7 | | | | | D04853J | 7 | | | ALL |
| 008 | 22 | PA | | 3-0 | SPARE | D04855J | | 34 | | | | | D04853J | 24 | | | ALL |
| 009 | 22 | PA | | 15-0 | 31-31-14 | D04855J | | 10 | | | | | D05207J | 10 | | | ALL |
| 010 | 24 | PK | | 15-0 | 31-31-15 | D04855J | | 11 | | | | | D05207J | 11 | | | ALL |
| 011 | 22 | PA | | 16-0 | 34-46-12 | D04853J | | 25 | | | | | D05207J | 15 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1600
Page 4
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1605 | 286T1605 | | | INTERSHELF L E1-3,E1-5,E2-3 DELTA (continued) | | | | | | | | | | | | | |
| 012 | 24 | | PK | 16-0 | 34-16-11 | D04853J | | 32 | | | | | S00591 | 7 | C | | 275-299 |
| 013 | 24 | | PK | 16-0 | 34-16-11 | D04853J | | 33 | | | | | S00591 | 8 | C | | 275-299 |
| 016 | 24 | | PK | 15-0 | 22-14-31 | D05207J | | 7 | | | | | D04855J | 40 | | | 050-099 |
| 016 | 24 | | PK | 15-0 | 22-14-31 | D04855J | | 40 | | | | | D05207J | 7 | | | 150-199, 275-299 |
| 017 | 24 | | PK | 15-0 | 31-31-19 | D05207J | | 17 | | | | | D04855J | 17 | | | ALL |
| 018 | 24 | | PK | 15-0 | 34-12-12 | D05207J | | 18 | | | | | D04855J | 38 | | | ALL |
| 019 | 24 | | PK | 3-0 | 34-46-12 | D04855J | | 45 | | | | | D04853J | 45 | | | ALL |
| 020 | 20 | | PA | 16-0 | 31-31-26 | D04853J | | 27 | | | | | D05207J | 24 | | | 050-099 |
| 020 | 24 | | PK | 16-0 | 31-31-26 | D04853J | | 27 | | | | | D05207J | 24 | | | 150-199, 275-299 |
| 021 | 20 | | PA | 15-0 | 34-12-12 | D04855J | | 33 | | | | | S00591 | 5 | C | | 275-299 |
| 022 | 20 | | PA | 2-0 | 34-12-12 | S00591 | | 6 | C | | | | GD00679 | D.. | E | | 275-299 |
| 023 | 24 | | PK | 3-0 | SPARE | D04855J | | 32 | | | | | D04853J | 22 | | | ALL |
| 024 | 24 | | PK | 3-0 | SPARE | D04855J | | 31 | | | | | D04853J | 21 | | | ALL |
| 025 | 24 | | PK | 3-0 | SPARE | D04855J | | 33 | | | | | D04853J | 23 | | | 150-199 |
| 028 | 22 | | PA | 15-0 | 31-31-14 | D05207J | | 31 | | | | | D04855J | 55 | | | ALL |
| 029 | 22 | | PA | 3-0 | 34-45-12 | D04853J | | 35 | | | | | D06143J | 8 | | | 150-152, 155-199, 275-299 |
| 029 | 22 | | PA | 3-0 | 34-45-12 | D04853J | | 35 | | | | | D05259J | 23 | | | 153-154 |
| 030 | 24 | | PK | 16-0 | 22-14-31 | D04853J | | 30 | | | | | D05207J | 30 | | | ALL |
| 031 | 22 | | PA | 16-0 | SPARE | D04853J | | 31 | | | | | D05207J | 16 | | | ALL |
| 032 | 22 | | PA | 16-0 | 31-31-26 | D04853J | | 26 | | | | | D05207J | 29 | | | 050-099 |
| 032 | 24 | | PK | 16-0 | 31-31-26 | D04853J | | 26 | | | | | D05207J | 29 | | | 150-199, 275-299 |
| 034 | 22 | | PA | 3-0 | 34-45-12 | D04853J | | 34 | | | | | D06143J | 7 | | | 150-152, 155-199, 275-299 |
| 034 | 22 | | PA | 3-0 | 34-45-12 | D04853J | | 34 | | | | | D05259J | 22 | | | 153-154 |
| 037 | 22 | | PA | 3-0 | SPARE | D04853J | | 28 | | | | | D04855J | 43 | | | 153-154 |
| 038 | 22 | | PA | 3-0 | SPARE | D04853J | | 29 | | | | | D04855J | 44 | | | 153-154 |
| 039 | 22 | | PA | 3-0 | 34-45-12 | D04853J | | 54 | | | | | D06143J | 9 | | | 050-099, 150-152, 155-199, 275-299 |
| 039 | 22 | | PA | 3-0 | 34-45-12 | D04853J | | 54 | | | | | D04855J | 54 | | | 153-154 |
| 201B | 24 | | PW | IA | 15-0 | 31-31-14 | | 2 | | | | | D05207J | 2 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 31-31-14 | | 1 | | | | | D05207J | 1 | | | ALL |
| 201Z | | | | IA | 0-0 | 31-31-14 | | 3 | | | | | D05207J | 3 | | | ALL |
| 202B | 24 | | PW | IB | 3-0 | 22-15-11 | | 23 | | | | | D04853J | 13 | | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 22-15-11 | | 22 | | | | | D04853J | 12 | | | ALL |
| 202Z | | | | IB | 0-0 | 22-15-11 | | 24 | | | | | D04853J | 14 | | | ALL |
| 203B | 24 | | PW | IC | 3-0 | SPARE | | 14 | | | | | D04853J | 4 | | | ALL |
| 203R | 24 | | PW | IC | 0-0 | SPARE | | 13 | | | | | D04853J | 3 | | | ALL |
| 203Z | | | | IC | 0-0 | SPARE | | 15 | | | | | D04853J | 5 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1600

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1605 | 286T1605 | | | INTERSHELF L E1-3,E1-5,E2-3 DELTA (continued) | | | | | | | | | | | |
| 204B | 24 | PW | ID | 15-0 | 31-31-14 | D04855J | | 5 | | D05207J | | 5 | | ALL | |
| 204R | 24 | PW | ID | 0-0 | 31-31-14 | D04855J | | 4 | | D05207J | | 4 | | ALL | |
| 204Z | | | ID | 0-0 | 31-31-14 | D04855J | | 6 | | D05207J | | 6 | | ALL | |
| 205B | 24 | PL | IE | 15-0 | SPARE | D04855J | | 9 | | D05207J | | 9 | | 050-099 | |
| 205B | 24 | PL | IE | 15-0 | 31-31-13 | D04855J | | 9 | | D05207J | | 9 | | 150-199, 275-299 | |
| 205R | 24 | PL | IE | 0-0 | 31-31-13 | D04855J | | 8 | | D05207J | | 8 | | ALL | |
| 206B | 24 | PW | IF | 3-0 | 34-46-12 | D04855J | | 26 | | D04853J | | 16 | | ALL | |
| 206R | 24 | PW | IF | 0-0 | 34-46-12 | D04855J | | 25 | | D04853J | | 15 | | ALL | |
| 206Z | | | IF | 0-0 | 34-46-12 | D04855J | | 27 | | D04853J | | 17 | | ALL | |
| 207B | 24 | PW | IG | 3-0 | 34-46-12 | D04855J | | 29 | | D04853J | | 19 | | ALL | |
| 207R | 24 | PW | IG | 0-0 | 34-46-12 | D04855J | | 28 | | D04853J | | 18 | | ALL | |
| 207Z | | | IG | 0-0 | 34-46-12 | D04855J | | 30 | | D04853J | | 20 | | ALL | |
| 209B | 24 | PW | II | 15-0 | 27-51-51 | D04855J | | 36 | | D05207J | | 13 | | ALL | |
| 209R | 24 | PW | II | 0-0 | 27-51-51 | D04855J | | 35 | | D05207J | | 12 | | ALL | |
| 209Z | | | II | 0-0 | 27-51-51 | D04855J | | 37 | | D05207J | | 14 | | ALL | |
| 210B | 24 | PW | IJ | 3-0 | SPARE | D04855J | | 42 | | D04853J | | 42 | | 150-199, 275-299 | |
| 210R | 24 | PW | IJ | 0-0 | SPARE | D04855J | | 41 | | D04853J | | 41 | | 150-199, 275-299 | |
| 210Z | | | IJ | 0-0 | SPARE | D04855J | | 39 | | D04853J | | 39 | | 150-199, 275-299 | |
| 213B | 22 | PB | IM | 15-0 | SPARE | D04855J | | 50 | | D05207J | | 23 | | 150-199 | |
| 213R | 22 | PB | IM | 0-0 | SPARE | D04855J | | 49 | | D05207J | | 19 | | 150-199 | |
| 217B | 24 | PW | IQ | 15-0 | 34-45-12 | D05207J | | 21 | | D04855J | | 52 | | 153-154 | |
| 217R | 24 | PW | IQ | 0-0 | 34-45-12 | D05207J | | 20 | | D04855J | | 51 | | 153-154 | |
| 217Z | | | IQ | 0-0 | 34-45-12 | D05207J | | 22 | | D04855J | | 53 | | 153-154 | |
| 218B | 24 | PW | IR | 15-0 | 34-45-12 | D05207J | | 26 | | D04855J | | 47 | | 153-154 | |
| 218R | 24 | PW | IR | 0-0 | 34-45-12 | D05207J | | 25 | | D04855J | | 46 | | 153-154 | |
| 218Z | | | IR | 0-0 | 34-45-12 | D05207J | | 27 | | D04855J | | 48 | | 153-154 | |
| 221B | 24 | PW | IU | 16-0 | 34-45-12 | D05207J | | 41 | | D06143J | | 5 | | 050-099, 150-152, 155-199, 275-299 | |
| 221R | 24 | PW | IU | 0-0 | 34-45-12 | D05207J | | 40 | | D06143J | | 4 | | 050-099, 150-152, 155-199, 275-299 | |
| 221Z | | | IU | 0-0 | 34-45-12 | D05207J | | 42 | | D06143J | | 6 | | 050-099, 150-152, 155-199, 275-299 | |
| 222B | 24 | PW | IV | 16-0 | 34-45-12 | D05207J | | 46 | | D06143J | | 2 | | 050-099, 150-152, 155-199, 275-299 | |
| 222R | 24 | PW | IV | 0-0 | 34-45-12 | D05207J | | 45 | | D06143J | | 1 | | 050-099, 150-152, 155-199, 275-299 | |
| 222Z | | | IV | 0-0 | 34-45-12 | D05207J | | 47 | | D06143J | | 3 | | 050-099, 150-152, 155-199, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W1600
Page 6 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|---------|----------|---------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1615 | 286T1615 | | | INTERSHELF R E1-3,E1-6,E2-3 DELTA | | | | | | | | | | | |
| 001 | 22 | | PA | | 4-0 | SPARE | D04683J | REF | JW | | D04769J | 17 | | | ALL |
| 002 | 22 | | PA | | 4-0 | SPARE | D04683J | REF | JW | | D04769J | 18 | | | ALL |
| 003 | 22 | | PA | | 4-0 | SPARE | D04683J | REF | JW | | D04769J | 19 | | | ALL |
| 006 | 24 | | PK | | 14-5 | | 34-45-13 | D04767J | | 36 | D04683J | 41 | | | 050-099, 150-199, 277-299 |
| 016 | 24 | | PK | | 14-5 | SPARE | D04683J | | | 16 | D04767J | 16 | | | 050-099 |
| 016 | 24 | | PK | | 14-5 | SPARE | D04683J | REF | JW | | D04767J | 16 | | | 150-199, 275-299 |
| 017 | 24 | | PK | | 14-5 | SPARE | D04683J | | | 17 | D04767J | 17 | | | 050-099 |
| 017 | 24 | | PK | | 14-5 | SPARE | D04683J | REF | JW | | D04767J | 17 | | | 150-199, 275-299 |
| 018 | 24 | | PK | | 14-5 | SPARE | D04683J | | | 18 | D04767J | 18 | | | 050-099 |
| 018 | 24 | | PK | | 14-5 | SPARE | D04683J | REF | JW | | D04767J | 18 | | | 150-199, 275-299 |
| 019 | 24 | | PK | | 14-5 | SPARE | D04683J | REF | JW | | D04767J | CAP | Y | | 150-152, 275-276 |
| 019 | 24 | | PK | | 14-5 | SPARE | D04683J | REF | JW | | D04767J | 19 | | | 153-154 |
| 020 | 24 | | PK | | 14-5 | SPARE | D04683J | | | 20 | D04767J | REF | JW | | ALL |
| 021 | 24 | | PK | | 14-5 | SPARE | D04683J | | | 21 | D04767J | REF | JW | | ALL |
| 025 | 22 | | PA | | 16-7 | SPARE | D04767J | CAP | Y | | D04769J | 28 | | | 050-099 |
| 026 | 22 | | PA | | 16-7 | SPARE | D04767J | CAP | Y | | D04769J | 29 | | | 050-099 |
| 028 | 24 | | PK | | 14-5 | SPARE | D04683J | CAP | Y | | D04767J | CAP | Y | | 050-099 |
| 029 | 24 | | PK | | 14-5 | SPARE | D04683J | CAP | Y | | D04767J | CAP | Y | | 050-099 |
| 031 | 20 | | PA | | 22-7 | | 34-12-22 | S00591 | | 2 | D04767J | 41 | | | 275-299 |
| 032 | 20 | | PA | | 1-9 | | 34-12-22 | S00591 | | 3 | GD00651 | D.. | E | | 275-299 |
| 036 | 22 | | PA | | 16-7 | SPARE | D04769J | | | 36 | D04767J | CAP | Y | | 150-154 |
| 036 | 22 | | PA | | 16-7 | SPARE | D04769J | | | 36 | D04767J | 36 | | | 275-276 |
| 037 | 24 | | PK | | 16-7 | | 34-21-21 | D04769J | | 37 | D04767J | 37 | | | ALL |
| 038 | 22 | | PA | | 16-7 | | 22-21-21 | D04769J | | 20 | D04767J | 42 | | | ALL |
| 039 | 22 | | PA | | 16-7 | SPARE | D04769J | | | 31 | D04767J | 43 | | | 050-099, 150-152, 155-199, 275-299 |
| 039 | 22 | | PA | | 16-7 | SPARE | D04769J | | | 31 | D04767J | REF | JW | | 153-154 |
| 040 | 22 | | PA | | 16-7 | | 34-21-21 | D04769J | | 38 | D04767J | 44 | | | ALL |
| 041 | 22 | | PA | | 16-7 | | 34-21-21 | D04769J | | 39 | D04767J | 45 | | | ALL |
| 042 | 22 | | PA | | 16-7 | | 34-21-21 | D04769J | | 40 | D04767J | 46 | | | ALL |
| 043 | 22 | | PA | | 16-7 | SPARE | D04769J | | | 41 | D04767J | 47 | | | ALL |
| 044 | 22 | | PA | | 16-7 | SPARE | D04769J | | | 13 | D04767J | CAP | Y | | 050-099 |
| 045 | 22 | | PA | | 16-7 | SPARE | D04769J | | | 14 | D04767J | CAP | Y | | 050-099 |
| 053 | 22 | | PA | | 16-7 | | 31-31-14 | D04769J | | 53 | D04767J | 53 | | | ALL |
| 060 | 22 | | PA | | 3-9 | | 34-12-62 | D03693J | | 1 | D03131 | 1 | | | 050-099 |
| 060 | 22 | | PA | | 6-0 | | 34-12-62 | D03693J | | 1 | D03131 | 1 | | | 150-199, 275-299 |
| 061 | 22 | | PA | | 3-9 | | 34-12-62 | D03693J | | 2 | D03131 | 2 | | | 050-099 |
| 061 | 22 | | PA | | 3-0 | | 34-12-62 | D03693J | | 2 | D03131 | 2 | | | 150-199, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1610

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1615 | 286T1615 | | | | INTERSHELF R E1-3,E1-6,E2-3 DELTA (continued) | | | | | | | | | | |
| 062 | 22 | | PA | | 3-9 | 34-12-62 | D03693J | | 5 | | D03131 | | 5 | | 050-099 |
| 062 | 22 | | PA | | 3-0 | 34-12-62 | D03693J | | 5 | | D03131 | | 5 | | 150-199, 275-299 |
| 063 | 22 | | PA | | 3-9 | 34-12-62 | D03693J | | 6 | | D03131 | | 6 | | 050-099 |
| 063 | 22 | | PA | | 3-0 | 34-12-62 | D03693J | | 6 | | D03131 | | 6 | | 150-199, 275-299 |
| 064 | 24 | | PK | | 3-9 | 34-12-62 | D03693J | | 7 | | D03131 | | 7 | | 050-099 |
| 064 | 24 | | PK | | 3-0 | 34-12-62 | D03693J | | 7 | | D03131 | | 7 | | 150-199, 275-299 |
| 065 | 24 | | PK | | 3-9 | 34-12-62 | D03693J | | 8 | | D03131 | | 8 | | 050-099 |
| 065 | 24 | | PK | | 3-0 | 34-12-62 | D03693J | | 8 | | D03131 | | 8 | | 150-199, 275-299 |
| 066 | 24 | | PK | | 3-9 | 34-12-62 | D03693J | | 9 | | D03131 | | 9 | | 050-099 |
| 066 | 24 | | PK | | 3-0 | 34-12-62 | D03693J | | 9 | | D03131 | | 9 | | 150-199, 275-299 |
| 067 | 24 | | PK | | 3-9 | 34-12-62 | D03693J | | 10 | | D03131 | | 10 | | 050-099 |
| 067 | 24 | | PK | | 3-0 | 34-12-62 | D03693J | | 10 | | D03131 | | 10 | | 150-199, 275-299 |
| 068 | 24 | | PK | | 3-9 | 34-12-62 | D03693J | | 11 | | D03131 | | 11 | | 050-099 |
| 068 | 24 | | PK | | 3-0 | 34-12-62 | D03693J | | 11 | | D03131 | | 11 | | 150-199, 275-299 |
| 069 | 24 | | PK | | 18-3 | 34-12-62 | D04683J | | 19 | | D03131 | | 12 | | 050-099 |
| 069 | 24 | | PK | | 21-0 | 34-12-62 | D04683J | | 19 | | D03131 | | 12 | | 150-199, 275-299 |
| 201B | 24 | | PW | IA | 16-7 | 34-61-25 | D04769J | | 2 | | D04767J | | 2 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-61-25 | D04769J | | 1 | | D04767J | | 1 | | ALL |
| 201Z | | | | IA | 0-0 | 34-61-25 | D04769J | | 3 | | D04767J | | 3 | | ALL |
| 202B | 24 | | PW | IB | 16-7 | 34-21-21 | D04769J | | 5 | | D04767J | | 5 | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-21-21 | D04769J | | 4 | | D04767J | | 4 | | ALL |
| 202Z | | | | IB | 0-0 | 34-21-21 | D04769J | | 6 | | D04767J | | 6 | | ALL |
| 203B | 24 | | PW | IC | 16-7 | 34-21-21 | D04769J | | 8 | | D04767J | | 8 | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 34-21-21 | D04769J | | 7 | | D04767J | | 7 | | ALL |
| 203Z | | | | IC | 0-0 | 34-21-21 | D04769J | | 9 | | D04767J | | 9 | | ALL |
| 204B | 24 | | PW | ID | 16-7 | 34-61-22 | D04769J | | 11 | | D04767J | | 11 | | ALL |
| 204R | 24 | | PW | ID | 0-0 | 34-61-22 | D04769J | | 10 | | D04767J | | 10 | | ALL |
| 204Z | | | | ID | 0-0 | 34-61-22 | D04769J | | 12 | | D04767J | | 12 | | ALL |
| 205B | 24 | | PW | IE | 14-5 | 22-32-11 | D04683J | | 3 | | D04767J | | 23 | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 22-32-11 | D04683J | | 2 | | D04767J | | 22 | | ALL |
| 205Z | | | | IE | 0-0 | 22-32-11 | D04683J | | 4 | | D04767J | | 24 | | ALL |
| 206B | 24 | | PW | IF | 14-5 | 22-32-11 | D04683J | | 14 | | D04767J | | 14 | | ALL |
| 206R | 24 | | PW | IF | 0-0 | 22-32-11 | D04683J | | 13 | | D04767J | | 13 | | ALL |
| 206Z | | | | IF | 0-0 | 22-32-11 | D04683J | | 15 | | D04767J | | 15 | | ALL |
| 207B | 24 | | PW | IG | 4-0 | 22-32-11 | D04683J | | 23 | | D04769J | | 23 | | ALL |
| 207R | 24 | | PW | IG | 0-0 | 22-32-11 | D04683J | | 22 | | D04769J | | 22 | | ALL |
| 207Z | | | | IG | 0-0 | 22-32-11 | D04683J | | 24 | | D04769J | | 24 | | ALL |
| 208B | 24 | | PW | IH | 4-0 | SPARE | D04683J | | 26 | | D04769J | | 26 | | ALL |
| 208R | 24 | | PW | IH | 0-0 | SPARE | D04683J | | 25 | | D04769J | | 25 | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W1610
 Page 2
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1615 | 286T1615 | | | INTERSHELF R E1-3,E1-6,E2-3 DELTA (continued) | | | | | | | | | | | |
| 208Z | | | | IH | 0-0 | SPARE | D04683J | 27 | | | D04769J | 27 | | | ALL |
| 209B | 24 | PW | IJ | | 14-5 | SPARE | D04683J | 11 | | | D04767J | 31 | | | 050-099 |
| 209B | 24 | PW | II | | 14-5 | SPARE | D04683J | 11 | | | D04767J | 31 | | | 150-199 |
| 209R | 24 | PW | IJ | | 0-0 | SPARE | D04683J | 10 | | | D04767J | 30 | | | 050-099 |
| 209R | 24 | PW | II | | 0-0 | SPARE | D04683J | 10 | | | D04767J | 30 | | | 150-199 |
| 209Z | | | | IJ | 0-0 | SPARE | D04683J | 12 | | | D04767J | 32 | | | 050-099 |
| 209Z | | | | II | 0-0 | SPARE | D04683J | 12 | | | D04767J | 32 | | | 150-199 |
| 210B | 24 | PW | IK | | 16-7 | 32-42-11 | D04769J | 34 | | | D04767J | 34 | | | 050-099 |
| 210B | 24 | PW | IJ | | 16-7 | 32-42-11 | D04769J | 34 | | | D04767J | 34 | | | 150-199, 275-299 |
| 210R | 24 | PW | IK | | 0-0 | 32-42-11 | D04769J | 33 | | | D04767J | 33 | | | 050-099 |
| 210R | 24 | PW | IJ | | 0-0 | 32-42-11 | D04769J | 33 | | | D04767J | 33 | | | 150-199, 275-299 |
| 210Z | | | | IK | 0-0 | 32-42-11 | D04769J | 35 | | | D04767J | 35 | | | 050-099 |
| 210Z | | | | IJ | 0-0 | 32-42-11 | D04769J | 35 | | | D04767J | 35 | | | 150-199, 275-299 |
| 211B | 24 | PW | IO | | 14-5 | 22-33-11 | D04683J | 30 | | | D04767J | 26 | | | 050-099 |
| 211B | 24 | PW | IK | | 14-5 | 22-33-11 | D04683J | 30 | | | D04767J | 26 | | | 150-199, 275-299 |
| 211R | 24 | PW | IO | | 0-0 | 22-33-11 | D04683J | 29 | | | D04767J | 25 | | | 050-099 |
| 211R | 24 | PW | IK | | 0-0 | 22-33-11 | D04683J | 29 | | | D04767J | 25 | | | 150-199, 275-299 |
| 211Z | | | | IO | 0-0 | 22-33-11 | D04683J | 28 | | | D04767J | 28 | | | 050-099 |
| 211Z | | | | IK | 0-0 | 22-33-11 | D04683J | 28 | | | D04767J | 28 | | | 150-199, 275-299 |
| 212B | 24 | PW | IL | | 14-5 | 22-33-11 | D04683J | 33 | | | D04767J | 49 | | | ALL |
| 212R | 24 | PW | IL | | 0-0 | 22-33-11 | D04683J | 32 | | | D04767J | 48 | | | ALL |
| 212Z | | | | IL | 0-0 | 22-33-11 | D04683J | 31 | | | D04767J | 29 | | | ALL |
| 213B | 24 | PW | IM | | 16-7 | 23-25-13 | D04769J | 44 | | | D04767J | 39 | | | 156-157, 166-199, 277-299 |
| 213B | 24 | PW | IM | | 14-5 | SPARE | D04683J | 39 | | | D04767J | 39 | | | 275-276 |
| 213R | 24 | PW | IM | | 0-0 | 23-25-13 | D04769J | 43 | | | D04767J | 38 | | | 156-157, 166-199, 277-299 |
| 213R | 24 | PW | IM | | 0-0 | SPARE | D04683J | 38 | | | D04767J | 38 | | | 275-276 |
| 213Z | | | | IM | 0-0 | 23-25-13 | D04769J | 42 | | | D04767J | 40 | | | 156-157, 166-199, 277-299 |
| 213Z | | | | IM | 0-0 | SPARE | D04683J | 40 | | | D04767J | 40 | | | 275-276 |
| 214B | 24 | PW | IN | | 16-7 | 34-21-31 | D04767J | 51 | | | D04769J | 16 | | | ALL |
| 214R | 24 | PW | IN | | 0-0 | 34-21-31 | D04767J | 50 | | | D04769J | 15 | | | ALL |
| 214Z | | | | IN | 0-0 | 34-21-31 | D04767J | 52 | | | D04769J | 32 | | | ALL |
| 219B | 24 | PW | IS | | 14-5 | 31-31-12 | D04767J | 27 | | | D04683J | 7 | | | 050-099 |
| 219B | 24 | PW | IS | | 17-0 | 31-31-12 | D04767J | 27 | | | D04683J | 7 | | | 150-152, 155-199, 275-299 |
| 219B | 24 | PW | IS | | 17-0 | 31-31-12 | D04767J | 43 | | | D04683J | 7 | | | 153-154 |
| 219R | 24 | PW | IS | | 0-0 | 31-31-12 | D04767J | 20 | | | D04683J | 8 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1610

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1615 | 286T1615 | | | INTERSHELF R E1-3,E1-6,E2-3 DELTA (continued) | | | | | | | | | | | |
| 219Z | | | | IS | 0-0 | 31-31-12 | D04767J | 21 | | | D04683J | 9 | | | ALL |
| 226B | 24 | PW | | JA | 14-5 | 34-45-14 | D04767J | 55 | | | D04683J | 6 | | | 050-099, 150-156, 162-166 |
| 226B | 24 | PW | | JA | 14-5 | SPARE | D04767J | 55 | | | D04683J | 6 | | | 157, 167-199, 277-299 |
| 226R | 24 | PW | | JA | 0-0 | 34-45-14 | D04767J | 54 | | | D04683J | 5 | | | 050-099, 150-156, 162-166 |
| 226R | 24 | PW | | JA | 0-0 | SPARE | D04767J | 54 | | | D04683J | 5 | | | 157, 167-199, 277-299 |
| 226Z | | | | JA | 0-0 | 34-45-14 | D04767J | 19 | | | D04683J | 37 | | | 050-099, 150-152, 155-156, 162-166 |
| 226Z | | | | JA | 0-0 | 34-45-14 | D04767J | 27 | | | D04683J | 37 | | | 153-154 |
| 226Z | | | | JA | 0-0 | SPARE | D04767J | 19 | | | D04683J | 37 | | | 157, 167-199, 277-299 |
| 230 | 20 | PA | | | 1-3 | 34-12-62 | GD07183 | S.. | E | | D03131 | REF | | JE | 050-099 |
| 230 | 20 | PA | | | 1-6 | 34-12-62 | GD07183 | S.. | E | | D03131 | REF | | JE | 150-199, 275-299 |
| 230B | 24 | PW | | JE | 3-9 | 34-12-62 | D03693J | 16 | | | D03131 | 34 | | | 050-099 |
| 230B | 24 | PW | | JE | 6-0 | 34-12-62 | D03693J | 16 | | | D03131 | 34 | | | 150-199, 275-299 |
| 230R | 24 | PW | | JE | 0-0 | 34-12-62 | D03693J | 17 | | | D03131 | 28 | | | ALL |
| 230Z | | | | JE | 0-0 | 34-12-62 | D03693J | 18 | | | D03131 | REF | | JE | ALL |
| 231 | 20 | PA | | | 1-3 | 34-12-62 | GD07183 | S.. | E | | D03131 | REF | | JF | 050-099 |
| 231 | 20 | PA | | | 1-6 | 34-12-62 | GD07183 | S.. | E | | D03131 | REF | | JF | 150-199, 275-299 |
| 231B | 24 | PW | | JF | 3-9 | 34-12-62 | D03693J | 19 | | | D03131 | 35 | | | 050-099 |
| 231B | 24 | PW | | JF | 6-0 | 34-12-62 | D03693J | 19 | | | D03131 | 35 | | | 150-199, 275-299 |
| 231R | 24 | PW | | JF | 0-0 | 34-12-62 | D03693J | 20 | | | D03131 | 29 | | | ALL |
| 231Z | | | | JF | 0-0 | 34-12-62 | D03693J | 21 | | | D03131 | REF | | JF | ALL |
| 232 | 20 | PA | | | 1-3 | 34-12-62 | GD07183 | S.. | E | | D03131 | REF | | JG | 050-099 |
| 232 | 20 | PA | | | 1-6 | 34-12-62 | GD07183 | S.. | E | | D03131 | REF | | JG | 150-199, 275-299 |
| 232B | 24 | PW | | JG | 18-3 | 34-12-62 | D04683J | 38 | | | D03131 | 36 | | | 050-099 |
| 232B | 24 | PW | | JG | 21-0 | 34-12-62 | D04683J | 16 | | | D03131 | 36 | | | 150-199, 275-299 |
| 232R | 24 | PW | | JG | 0-0 | 34-12-62 | D04683J | 39 | | | D03131 | 30 | | | 050-099 |
| 232R | 24 | PW | | JG | 0-0 | 34-12-62 | D04683J | 17 | | | D03131 | 30 | | | 150-199, 275-299 |
| 232Z | | | | JG | 0-0 | 34-12-62 | D04683J | 40 | | | D03131 | REF | | JG | 050-099 |
| 232Z | | | | JG | 0-0 | 34-12-62 | D04683J | 18 | | | D03131 | REF | | JG | 150-199, 275-299 |
| W1619 | 286T1619 | | | INTERSHELF E1-5,E2-3 | | | | | | | | | | | |
| 001 | 24 | PK | | | 17-0 | 34-31-21 | D04805J | 1 | | | D04821J | 1 | | | ALL |
| 002 | 24 | PK | | | 17-0 | SPARE | D04805J | 38 | | | D04821J | 38 | | | ALL |
| 003 | 22 | PA | | | 17-0 | 31-31-18 | D04805J | 43 | | | D04821J | 43 | | | ALL |
| 004 | 22 | PA | | | 17-0 | 31-31-18 | D04805J | 44 | | | D04821J | 44 | | | ALL |
| 005 | 22 | PA | | | 17-0 | 31-31-18 | D04805J | 45 | | | D04821J | 45 | | | ALL |
| 006 | 22 | PA | | | 17-0 | 31-31-18 | D04805J | 46 | | | D04821J | 46 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1610
Page 4
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1619 | 286T1619 | | | INTERSHELF E1-5,E2-3 (continued) | | | | | | | | | | | | | |
| 011 | 22 | | PA | | 17-0 | 34-22-26 | D04805J | | 55 | | | | D04821J | 55 | | | ALL |
| 039 | 24 | | PK | | 17-0 | SPARE | D04805J | | 39 | | | | D04821J | 39 | | | ALL |
| 049 | 24 | | PK | | 17-0 | SPARE | D04805J | | 49 | | | | D04821J | 49 | | | ALL |
| 201B | 24 | | PW | IA | 17-0 | 34-61-24 | D04805J | | 3 | | | | D04821J | 3 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 34-61-24 | D04805J | | 2 | | | | D04821J | 2 | | | ALL |
| 201Z | | | | IA | 0-0 | 34-61-24 | D04805J | | 4 | | | | D04821J | 4 | | | ALL |
| 202B | 24 | | PW | IB | 17-0 | 34-61-24 | D04805J | | 6 | | | | D04821J | 6 | | | ALL |
| 202R | 24 | | PW | IB | 0-0 | 34-61-24 | D04805J | | 5 | | | | D04821J | 5 | | | ALL |
| 202Z | | | | IB | 0-0 | 34-61-24 | D04805J | | 7 | | | | D04821J | 7 | | | ALL |
| 203B | 24 | | PW | IC | 17-0 | 34-22-28 | D04805J | | 9 | | | | D04821J | 9 | | | ALL |
| 203R | 24 | | PW | IC | 0-0 | 34-22-28 | D04805J | | 8 | | | | D04821J | 8 | | | ALL |
| 203Z | | | | IC | 0-0 | 34-22-28 | D04805J | | 10 | | | | D04821J | 10 | | | ALL |
| 204B | 24 | | PW | ID | 17-0 | 34-61-25 | D04805J | | 12 | | | | D04821J | 12 | | | 050-099 |
| 204B | 24 | | PW | ID | 17-0 | 34-61-26 | D04805J | | 12 | | | | D04821J | 12 | | | 150-199, 275-299 |
| 204R | 24 | | PW | ID | 0-0 | 34-61-25 | D04805J | | 11 | | | | D04821J | 11 | | | 050-099 |
| 204R | 24 | | PW | ID | 0-0 | 34-61-26 | D04805J | | 11 | | | | D04821J | 11 | | | 150-199, 275-299 |
| 204Z | | | | ID | 0-0 | 34-61-26 | D04805J | | 13 | | | | D04821J | 13 | | | ALL |
| 205B | 24 | | PW | IE | 17-0 | 34-61-26 | D04805J | | 15 | | | | D04821J | 15 | | | ALL |
| 205R | 24 | | PW | IE | 0-0 | 34-61-26 | D04805J | | 14 | | | | D04821J | 14 | | | ALL |
| 205Z | | | | IE | 0-0 | 34-61-26 | D04805J | | 16 | | | | D04821J | 16 | | | ALL |
| 206B | 24 | | PW | IF | 17-0 | 34-22-29 | D04805J | | 18 | | | | D04821J | 18 | | | ALL |
| 206R | 24 | | PW | IF | 0-0 | 34-22-29 | D04805J | | 17 | | | | D04821J | 17 | | | ALL |
| 206Z | | | | IF | 0-0 | 34-22-29 | D04805J | | 19 | | | | D04821J | 19 | | | ALL |
| 207B | 24 | | PW | IG | 17-0 | 34-22-29 | D04805J | | 21 | | | | D04821J | 21 | | | ALL |
| 207R | 24 | | PW | IG | 0-0 | 34-22-29 | D04805J | | 20 | | | | D04821J | 20 | | | ALL |
| 207Z | | | | IG | 0-0 | 34-22-29 | D04805J | | 22 | | | | D04821J | 22 | | | ALL |
| 208B | 24 | | PW | IH | 17-0 | 34-61-22 | D04805J | | 23 | | | | D04821J | 23 | | | ALL |
| 208R | 24 | | PW | IH | 0-0 | 34-61-22 | D04805J | | 24 | | | | D04821J | 24 | | | ALL |
| 208Z | | | | IH | 0-0 | 34-61-22 | D04805J | | 25 | | | | D04821J | 25 | | | ALL |
| 209B | 24 | | PW | II | 17-0 | 34-61-22 | D04805J | | 27 | | | | D04821J | 27 | | | ALL |
| 209R | 24 | | PW | II | 0-0 | 34-61-22 | D04805J | | 26 | | | | D04821J | 26 | | | ALL |
| 209Z | | | | II | 0-0 | 34-61-22 | D04805J | | 28 | | | | D04821J | 28 | | | ALL |
| 210B | 24 | | PW | IJ | 17-0 | 34-12-22 | D04805J | | 30 | | | | D04821J | 30 | | | ALL |
| 210R | 24 | | PW | IJ | 0-0 | 34-12-22 | D04805J | | 29 | | | | D04821J | 29 | | | ALL |
| 210Z | | | | IJ | 0-0 | 34-12-22 | D04805J | | 31 | | | | D04821J | 31 | | | ALL |
| 211B | 24 | | PW | IK | 17-0 | 34-31-21 | D04805J | | 33 | | | | D04821J | 33 | | | ALL |
| 211R | 24 | | PW | IK | 0-0 | 34-31-21 | D04805J | | 32 | | | | D04821J | 32 | | | ALL |
| 211Z | | | | IK | 0-0 | 34-31-21 | D04805J | | 34 | | | | D04821J | 34 | | | ALL |
| 212B | 24 | | PW | IL | 17-0 | 34-58-22 | D04805J | | 36 | | | | D04821J | 36 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1610

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1619 | 286T1619 | | | INTERSHELF E1-5,E2-3 (continued) | | | | | | | | | | | |
| 212R | 24 | PW | IL | | 0-0 | 34-58-22 | D04805J | | 35 | | D04821J | | 35 | | ALL |
| 212Z | | | IL | | 0-0 | 34-58-22 | D04805J | | 37 | | D04821J | | 37 | | ALL |
| 213B | 24 | PW | IM | | 17-0 | SPARE | D04805J | | 41 | | D04821J | | 41 | | ALL |
| 213R | 24 | PW | IM | | 0-0 | SPARE | D04805J | | 40 | | D04821J | | 40 | | ALL |
| 213Z | | | IM | | 0-0 | SPARE | D04805J | | 42 | | D04821J | | 42 | | ALL |
| 216B | 24 | PW | IP | | 17-0 | SPARE | D04821J | | 51 | | D04805J | | 51 | | 150-199 |
| 216R | 24 | PW | IP | | 0-0 | SPARE | D04821J | | 50 | | D04805J | | 50 | | 150-199 |
| 216Z | | | IP | | 0-0 | SPARE | D04821J | | 52 | | D04805J | | 52 | | 150-199 |

WIRE LIST
D280T132

91-21-11
Section W1610
Page 6 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1633 | 286T1633 | | | INTERSHELF L,E1-3,E2-2,E2-5 | | | | | | | | | | | | |
| 001 | 24 | PV | AA | | 5-0 | 23-51-12 | D04735J | | 1 | | | D04737J | | 1 | | 050-099, 150-152 |
| 001 | 24 | PV | AA | | 4-3 | 23-51-12 | D04735J | | 1 | | | D04737J | | 1 | | 153-154, 275-276 |
| 001 | 24 | PV | AA | | 4-4 | 23-51-12 | D04735J | | 1 | | | D04737J | | 1 | | 155-199, 277-299 |
| 001Z | | | AA | | 0-0 | 23-51-12 | D04735J | | 3 | | | D04737J | | 3 | | ALL |
| 002 | 24 | PV | AB | | 5-0 | 23-51-12 | D04735J | | 2 | | | D04737J | | 2 | | 050-099, 150-152 |
| 002 | 24 | PV | AB | | 4-3 | 23-51-12 | D04735J | | 2 | | | D04737J | | 2 | | 153-154, 275-276 |
| 002 | 24 | PV | AB | | 4-4 | 23-51-12 | D04735J | | 2 | | | D04737J | | 2 | | 155-199, 277-299 |
| 002Z | | | AB | | 0-0 | 23-51-12 | D04735J | | 4 | | | D04737J | | 4 | | ALL |
| 003 | 24 | PV | AC | | 18-0 | 23-51-13 | D04737J | | 14 | | | D04781J | | 24 | | 050-099, 150-152 |
| 003 | 24 | PV | AC | | 16-0 | 23-51-13 | D04737J | | 14 | | | D04781J | | 24 | | 153-199, 275-299 |
| 003Z | | | AC | | 0-0 | 23-51-13 | D04737J | | 15 | | | D04781J | | 25 | | ALL |
| 004 | 24 | PK | | | 5-0 | SPARE | D04737J | | 16 | | | D04735J | | 39 | | 150-152 |
| 004 | 24 | PK | | | 4-3 | SPARE | D04737J | | 16 | | | D04735J | | 39 | | 153-154 |
| 005 | 24 | PK | | | 14-0 | 34-55-11 | D04735J | | 34 | | | D04781J | | 27 | | 050-099 |
| 005 | 24 | PK | | | 15-0 | 34-55-11 | D04735J | | 34 | | | D04781J | | 27 | | 150-152 |
| 005 | 24 | PK | | | 13-4 | 34-55-11 | D04735J | | 34 | | | D04781J | | 27 | | 153-154, 275-276 |
| 005 | 24 | PK | | | 13-5 | 34-55-11 | D04735J | | 34 | | | D04781J | | 27 | | 155-199, 277-299 |
| 006 | 24 | PK | | | 18-0 | SPARE | D04737J | | 17 | | | D04781J | | 31 | | 050-099, 150-152 |
| 006 | 24 | PK | | | 16-0 | SPARE | D04737J | | 17 | | | D04781J | | 31 | | 153-199, 275-299 |
| 016 | 24 | PV | AP | | 18-0 | 23-51-13 | D04737J | | 21 | | | D04781J | | 1 | | 050-099, 150-152 |
| 016 | 24 | PV | AP | | 16-0 | 23-51-13 | D04737J | | 21 | | | D04781J | | 1 | | 153-199, 275-299 |
| 016Z | | | AP | | 0-0 | 23-51-13 | D04737J | | 22 | | | D04781J | | 2 | | ALL |
| 018 | 22 | PA | | | 14-0 | 34-61-14 | D04735J | | 55 | | | D04781J | | 55 | | 050-099 |
| 018 | 22 | PA | | | 15-0 | 34-61-14 | D04735J | | 55 | | | D04781J | | 55 | | 150-152 |
| 018 | 22 | PA | | | 13-4 | 34-61-14 | D04735J | | 55 | | | D04781J | | 55 | | 153-154, 275-276 |
| 018 | 22 | PA | | | 13-5 | 34-61-14 | D04735J | | 55 | | | D04781J | | 55 | | 155-199, 277-299 |
| 021 | 22 | PA | | | 12-6 | SPARE | D04681J | | 8 | | | D04781J | | 45 | | 153-154 |
| 201B | 24 | PW | IA | | 5-0 | 23-51-12 | D04735J | | 6 | | | D04737J | | 6 | | 050-099, 150-152 |
| 201B | 24 | PW | IA | | 4-3 | 23-51-12 | D04735J | | 6 | | | D04737J | | 6 | | 153-154, 275-276 |
| 201B | 24 | PW | IA | | 4-4 | 23-51-12 | D04735J | | 6 | | | D04737J | | 6 | | 155-199, 277-299 |
| 201R | 24 | PW | IA | | 0-0 | 23-51-12 | D04735J | | 5 | | | D04737J | | 5 | | ALL |
| 201Z | | | IA | | 0-0 | 23-51-12 | D04735J | | 7 | | | D04737J | | 7 | | ALL |
| 202B | 24 | PW | IB | | 5-0 | 34-61-15 | D04735J | | 9 | | | D04737J | | 9 | | 050-099, 150-152 |
| 202B | 24 | PW | IB | | 4-3 | 34-61-15 | D04735J | | 9 | | | D04737J | | 9 | | 153-154, 275-276 |
| 202B | 24 | PW | IB | | 4-4 | 34-61-15 | D04735J | | 9 | | | D04737J | | 9 | | 155-199, 277-299 |
| 202R | 24 | PW | IB | | 0-0 | 34-61-15 | D04735J | | 8 | | | D04737J | | 8 | | ALL |
| 202Z | | | IB | | 0-0 | 34-61-15 | D04735J | | 49 | | | D04737J | | 23 | | ALL |
| 203B | 24 | PW | IC | | 5-0 | 34-61-15 | D04735J | | 11 | | | D04737J | | 11 | | 050-099, 150-152 |
| 203B | 24 | PW | IC | | 4-3 | 34-61-15 | D04735J | | 11 | | | D04737J | | 11 | | 153-154, 275-276 |

WIRE LIST

D280T132

91-21-11

Section W1630

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1633 | 286T1633 | | | INTERSHELF L,E1-3,E2-2,E2-5 (continued) | | | | | | | | | | | |
| 203B | 24 | PW | IC | 4-4 | 34-61-15 | D04735J | 11 | | | D04737J | 11 | | | 155-199, 277-299 | |
| 203R | 24 | PW | IC | 0-0 | 34-61-15 | D04735J | 10 | | | D04737J | 10 | | | ALL | |
| 203Z | | | IC | 0-0 | 34-61-15 | D04735J | 12 | | | D04737J | 12 | | | ALL | |
| 204B | 24 | PW | ID | 14-0 | 34-31-11 | D04735J | 13 | | | D04781J | 3 | | | 050-099 | |
| 204B | 24 | PW | ID | 15-0 | 34-31-11 | D04735J | 13 | | | D04781J | 3 | | | 150-152 | |
| 204B | 24 | PW | ID | 13-4 | 34-31-11 | D04735J | 13 | | | D04781J | 3 | | | 153-154, 275-276 | |
| 204B | 24 | PW | ID | 13-5 | 34-31-11 | D04735J | 13 | | | D04781J | 3 | | | 155-199, 277-299 | |
| 204R | 24 | PW | ID | 0-0 | 34-31-11 | D04735J | 14 | | | D04781J | 4 | | | ALL | |
| 204Z | | | ID | 0-0 | 34-31-11 | D04735J | 15 | | | D04781J | 5 | | | ALL | |
| 205B | 24 | PW | IE | 14-0 | 34-12-12 | D04735J | 17 | | | D04781J | 7 | | | 050-099 | |
| 205B | 24 | PW | IE | 15-0 | 34-12-12 | D04735J | 17 | | | D04781J | 7 | | | 150-152 | |
| 205B | 24 | PW | IE | 13-4 | 34-12-12 | D04735J | 17 | | | D04781J | 7 | | | 153-154, 275-276 | |
| 205B | 24 | PW | IE | 13-5 | 34-12-12 | D04735J | 17 | | | D04781J | 7 | | | 155-199, 277-299 | |
| 205R | 24 | PW | IE | 0-0 | 34-12-12 | D04735J | 16 | | | D04781J | 6 | | | ALL | |
| 205Z | | | IE | 0-0 | 34-12-12 | D04735J | 18 | | | D04781J | 8 | | | ALL | |
| 206B | 24 | PW | IF | 14-0 | 34-61-15 | D04735J | 20 | | | D04781J | 10 | | | 050-099 | |
| 206B | 24 | PW | IF | 15-0 | 34-61-15 | D04735J | 20 | | | D04781J | 10 | | | 150-152 | |
| 206B | 24 | PW | IF | 13-4 | 34-61-15 | D04735J | 20 | | | D04781J | 10 | | | 153-154, 275-276 | |
| 206B | 24 | PW | IF | 13-5 | 34-61-15 | D04735J | 20 | | | D04781J | 10 | | | 155-199, 277-299 | |
| 206R | 24 | PW | IF | 0-0 | 34-61-15 | D04735J | 19 | | | D04781J | 9 | | | ALL | |
| 206Z | | | IF | 0-0 | 34-61-15 | D04735J | 21 | | | D04781J | 11 | | | ALL | |
| 207B | 24 | PW | IG | 14-0 | 22-32-11 | D04735J | 23 | | | D04781J | 13 | | | 050-099 | |
| 207B | 24 | PW | IG | 15-0 | 22-32-11 | D04735J | 23 | | | D04781J | 13 | | | 150-152 | |
| 207B | 24 | PW | IG | 13-4 | 22-32-11 | D04735J | 23 | | | D04781J | 13 | | | 153-154, 275-276 | |
| 207B | 24 | PW | IG | 13-5 | 22-32-11 | D04735J | 23 | | | D04781J | 13 | | | 155-199, 277-299 | |
| 207R | 24 | PW | IG | 0-0 | 22-32-11 | D04735J | 22 | | | D04781J | 12 | | | ALL | |
| 207Z | | | IG | 0-0 | 22-32-11 | D04735J | 24 | | | D04781J | 14 | | | ALL | |
| 208B | 24 | PW | IH | 14-0 | 34-61-12 | D04735J | 26 | | | D04781J | 16 | | | 050-099 | |
| 208B | 24 | PW | IH | 15-0 | 34-61-12 | D04735J | 26 | | | D04781J | 16 | | | 150-152 | |
| 208B | 24 | PW | IH | 13-4 | 34-61-12 | D04735J | 26 | | | D04781J | 16 | | | 153-154, 275-276 | |
| 208B | 24 | PW | IH | 13-5 | 34-61-12 | D04735J | 26 | | | D04781J | 16 | | | 155-199, 277-299 | |
| 208R | 24 | PW | IH | 0-0 | 34-61-12 | D04735J | 25 | | | D04781J | 15 | | | ALL | |
| 208Z | | | IH | 0-0 | 34-61-12 | D04735J | 27 | | | D04781J | 17 | | | ALL | |
| 209B | 24 | PW | II | 14-0 | 34-61-12 | D04735J | 29 | | | D04781J | 19 | | | 050-099 | |
| 209B | 24 | PW | II | 15-0 | 34-61-12 | D04735J | 29 | | | D04781J | 19 | | | 150-152 | |
| 209B | 24 | PW | II | 13-4 | 34-61-12 | D04735J | 29 | | | D04781J | 19 | | | 153-154, 275-276 | |
| 209B | 24 | PW | II | 13-5 | 34-61-12 | D04735J | 29 | | | D04781J | 19 | | | 155-199, 277-299 | |
| 209R | 24 | PW | II | 0-0 | 34-61-12 | D04735J | 28 | | | D04781J | 18 | | | ALL | |
| 209Z | | | II | 0-0 | 34-61-12 | D04735J | 30 | | | D04781J | 20 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1630

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|---------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1633 | 286T1633 | | | INTERSHELF L,E1-3,E2-2,E2-5 (continued) | | | | | | | | | | | | |
| 210B | 24 | PW | IJ | 14-0 | 34-61-14 | D04735J | | 32 | | | | D04781J | 22 | | 050-099 | |
| 210B | 24 | PW | IJ | 15-0 | 34-61-14 | D04735J | | 32 | | | | D04781J | 22 | | 150-152 | |
| 210B | 24 | PW | IJ | 13-4 | 34-61-14 | D04735J | | 32 | | | | D04781J | 22 | | 153-154, 275-276 | |
| 210B | 24 | PW | IJ | 13-5 | 34-61-14 | D04735J | | 32 | | | | D04781J | 22 | | 155-199, 277-299 | |
| 210R | 24 | PW | IJ | 0-0 | 34-61-14 | D04735J | | 31 | | | | D04781J | 21 | | ALL | |
| 210Z | | | IJ | 0-0 | 34-61-14 | D04735J | | 33 | | | | D04781J | 23 | | ALL | |
| 212B | 24 | PW | IL | 5-0 | 23-22-11 | D04737J | | 19 | | | | D04735J | 41 | | 050-099, 150-152 | |
| 212B | 24 | PW | IL | 4-3 | 23-22-11 | D04737J | | 19 | | | | D04735J | 41 | | 153-154, 275-276 | |
| 212B | 24 | PW | IL | 4-4 | 23-22-11 | D04737J | | 19 | | | | D04735J | 41 | | 155-199, 277-299 | |
| 212R | 24 | PW | IL | 0-0 | 23-22-11 | D04737J | | 18 | | | | D04735J | 38 | | ALL | |
| 212Z | | | IL | 0-0 | 23-22-11 | D04737J | | 20 | | | | D04735J | 40 | | ALL | |
| 213B | 24 | PW | IM | 15-0 | 34-61-12 | D04735J | | 52 | | | | D04781J | 52 | | 050-099, 150-152 | |
| 213B | 24 | PW | IM | 13-4 | 34-61-12 | D04735J | | 52 | | | | D04781J | 52 | | 153-154, 275-276 | |
| 213B | 24 | PW | IM | 13-5 | 34-61-12 | D04735J | | 52 | | | | D04781J | 52 | | 155-199, 277-299 | |
| 213R | 24 | PW | IM | 0-0 | 34-61-12 | D04735J | | 51 | | | | D04781J | 51 | | ALL | |
| 213Z | | | IM | 0-0 | 34-61-12 | D04735J | | 53 | | | | D04781J | 53 | | ALL | |
| 215B | 24 | PW | IO | 5-0 | 31-35-11 | D04737J | | 25 | | | | D04735J | 43 | | 050-099 | |
| 215B | 24 | PW | IO | 6-0 | 31-35-11 | D04737J | | 25 | | | | D04735J | 43 | | 150-152 | |
| 215B | 24 | PW | IO | 4-3 | 31-35-11 | D04737J | | 25 | | | | D04735J | 43 | | 153-154, 275-276 | |
| 215B | 24 | PW | IO | 4-4 | 31-35-11 | D04737J | | 25 | | | | D04735J | 43 | | 155-199, 277-299 | |
| 215R | 24 | PW | IO | 0-0 | 31-35-11 | D04737J | | 24 | | | | D04735J | 42 | | ALL | |
| 215Z | | | IO | 0-0 | 31-35-11 | D04737J | | 26 | | | | D04735J | 44 | | ALL | |
| 216B | 24 | PW | IP | 13-0 | 31-35-12 | D04781J | | 33 | | | | D04229J | 2 | | 050-099 | |
| 216B | 24 | PW | IP | 14-0 | 31-35-12 | D04781J | | 33 | | | | D04229J | 2 | | 150-152 | |
| 216B | 24 | PW | IP | 13-1 | 31-35-12 | D04781J | | 33 | | | | D04229J | 2 | | 153-154, 275-276 | |
| 216B | 24 | PW | IP | 12-6 | 31-35-12 | D04781J | | 33 | | | | D04229J | 2 | | 155-199, 277-299 | |
| 216R | 24 | PW | IP | 0-0 | 31-35-12 | D04781J | | 32 | | | | D04229J | 1 | | ALL | |
| 216Z | | | IP | 0-0 | 31-35-12 | D04781J | | 34 | | | | D04229J | 3 | | ALL | |
| 217B | 24 | PW | IQ | 13-0 | 31-35-12 | D04781J | | 36 | | | | D04229J | 5 | | 050-099 | |
| 217B | 24 | PW | IQ | 14-0 | 31-35-12 | D04781J | | 36 | | | | D04229J | 5 | | 150-152 | |
| 217B | 24 | PW | IQ | 13-1 | 31-35-12 | D04781J | | 36 | | | | D04229J | 5 | | 153-154, 275-276 | |
| 217B | 24 | PW | IQ | 12-6 | 31-35-12 | D04781J | | 36 | | | | D04229J | 5 | | 155-199, 277-299 | |
| 217R | 24 | PW | IQ | 0-0 | 31-35-12 | D04781J | | 35 | | | | D04229J | 4 | | ALL | |
| 217Z | | | IQ | 0-0 | 31-35-12 | D04781J | | 37 | | | | D04229J | 6 | | ALL | |
| 218B | 24 | PW | IR | 13-0 | 31-35-12 | D04781J | | 29 | | | | D04229J | 8 | | 050-099 | |
| 218B | 24 | PW | IR | 14-0 | 31-35-12 | D04781J | | 29 | | | | D04229J | 8 | | 150-152 | |
| 218B | 24 | PW | IR | 13-1 | 31-35-12 | D04781J | | 29 | | | | D04229J | 8 | | 153-154, 275-276 | |
| 218B | 24 | PW | IR | 12-6 | 31-35-12 | D04781J | | 29 | | | | D04229J | 8 | | 155-199, 277-299 | |
| 218R | 24 | PW | IR | 0-0 | 31-35-12 | D04781J | | 28 | | | | D04229J | 7 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1630

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1633 | 286T1633 | | | INTERSHELF L,E1-3,E2-2,E2-5 (continued) | | | | | | | | | | | | |
| 218Z | | | | IR | 0-0 | 31-35-12 | D04781J | | 30 | | D04229J | | 9 | | ALL | |
| 219B | 24 | | PW | IS | 5-0 | 31-35-13 | D04737J | | 34 | | D04735J | | 46 | | 050-099 | |
| 219B | 24 | | PW | IS | 6-0 | 31-35-13 | D04737J | | 34 | | D04735J | | 46 | | 150-152 | |
| 219B | 24 | | PW | IS | 4-3 | 31-35-13 | D04737J | | 34 | | D04735J | | 46 | | 153-154, 275-276 | |
| 219B | 24 | | PW | IS | 4-4 | 31-35-13 | D04737J | | 34 | | D04735J | | 46 | | 155-199, 277-299 | |
| 219R | 24 | | PW | IS | 0-0 | 31-35-13 | D04737J | | 33 | | D04735J | | 45 | | ALL | |
| 219Z | | | | IS | 0-0 | 31-35-13 | D04737J | | 35 | | D04735J | | 47 | | ALL | |
| 220B | 24 | | PW | IT | 5-0 | 31-36-11 | D04737J | | 31 | | D04735J | | 36 | | 050-099 | |
| 220B | 24 | | PW | IT | 6-0 | 31-36-11 | D04737J | | 31 | | D04735J | | 36 | | 150-152 | |
| 220B | 24 | | PW | IT | 4-3 | 31-36-11 | D04737J | | 31 | | D04735J | | 36 | | 153-154, 275-276 | |
| 220B | 24 | | PW | IT | 4-4 | 31-36-11 | D04737J | | 31 | | D04735J | | 36 | | 155-199, 277-299 | |
| 220R | 24 | | PW | IT | 0-0 | 31-36-11 | D04737J | | 30 | | D04735J | | 35 | | ALL | |
| 220Z | | | | IT | 0-0 | 31-36-11 | D04737J | | 32 | | D04735J | | 37 | | ALL | |
| 222B | 24 | | PW | IV | 5-0 | 23-22-12 | D04735J | | 54 | | D04737J | | 28 | | 050-099, 150-152 | |
| 222B | 24 | | PW | IV | 4-3 | 23-22-12 | D04735J | | 54 | | D04737J | | 28 | | 153-154, 275-276 | |
| 222B | 24 | | PW | IV | 4-4 | 23-22-12 | D04735J | | 54 | | D04737J | | 28 | | 155-199, 277-299 | |
| 222R | 24 | | PW | IV | 0-0 | 23-22-12 | D04735J | | 50 | | D04737J | | 27 | | ALL | |
| 222Z | | | | IV | 0-0 | 23-22-12 | D04735J | | 48 | | D04737J | | 29 | | ALL | |
| 225B | 24 | | PW | IY | 14-0 | 34-45-14 | D04229J | | 11 | | D05827J | | 5 | | 050-099 | |
| 225B | 24 | | PW | IY | 15-0 | 34-45-14 | D04229J | | 11 | | D05827J | | 5 | | 150-152 | |
| 225B | 24 | | PW | IY | 13-1 | 34-45-14 | D04229J | | 11 | | D04781J | | 43 | | 153-154 | |
| 225B | 24 | | PW | IY | 13-6 | 34-45-14 | D04229J | | 11 | | D05827J | | 5 | | 155-199, 277-299 | |
| 225R | 24 | | PW | IY | 0-0 | 34-45-14 | D04229J | | 10 | | D05827J | | 4 | | 050-099, 150-152, 155-199, 277-299 | |
| 225R | 24 | | PW | IY | 0-0 | 34-45-14 | D04229J | | 10 | | D04781J | | 42 | | 153-154 | |
| 225Z | | | | IY | 0-0 | 34-45-14 | D04229J | | 12 | | D05827J | | 6 | | 050-099, 150-152, 155-199, 277-299 | |
| 225Z | | | | IY | 0-0 | 34-45-14 | D04229J | | 12 | | D04781J | | 44 | | 153-154 | |
| 226B | 24 | | PW | JA | 13-1 | SPARE | D04229J | | 14 | | D04781J | | 50 | | 153-154 | |
| 226B | 24 | | PW | JA | 12-6 | SPARE | D04229J | | 14 | | D04781J | | 50 | | 155-199 | |
| 226R | 24 | | PW | JA | 0-0 | SPARE | D04229J | | 13 | | D04781J | | 49 | | 153-199 | |
| 226Z | | | | JA | 0-0 | SPARE | D04229J | | 15 | | D04781J | | 54 | | 153-199 | |
| 227B | 24 | | PW | JB | 13-0 | 34-45-12 | D04681J | | 10 | | D04781J | | 48 | | 050-099, 150-152 | |
| 227B | 24 | | PW | JB | 12-6 | 34-45-12 | D04681J | | 10 | | D04781J | | 48 | | 153-199, 277-299 | |
| 227B | 24 | | PW | JB | 12-6 | SPARE | D04681J | | 10 | | D04781J | | 48 | | 275-276 | |
| 227R | 24 | | PW | JB | 0-0 | 34-45-12 | D04681J | | 9 | | D04781J | | 47 | | 050-099, 150-199, 277-299 | |
| 227R | 24 | | PW | JB | 0-0 | SPARE | D04681J | | 9 | | D04781J | | 47 | | 275-276 | |

WIRE LIST

D280T132

91-21-11
Section W1630
Page 4
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|---------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1633 | 286T1633 | | | | INTERSHELF L,E1-3,E2-2,E2-5 (continued) | | | | | | | | | | | |
| 227Z | | | | JB | 0-0 | 34-45-12 | D04681J | | 11 | | | D04781J | 46 | | 050-099, 150-199, 277-299 | |
| 227Z | | | | JB | 0-0 | SPARE | D04681J | | 11 | | | D04781J | 46 | | 275-276 | |
| 228B | 24 | PW | JC | | 14-0 | 34-45-12 | D04681J | | 13 | | | D05827J | 2 | | 050-099, 150-152 | |
| 228B | 24 | PW | JC | | 12-6 | 34-45-12 | D04681J | | 13 | | | D04781J | 40 | | 153-154 | |
| 228B | 24 | PW | JC | | 13-6 | 34-45-12 | D04681J | | 13 | | | D05827J | 2 | | 155-199, 277-299 | |
| 228R | 24 | PW | JC | | 0-0 | 34-45-12 | D04681J | | 12 | | | D05827J | 1 | | 050-099, 150-152, 155-199, 277-299 | |
| 228R | 24 | PW | JC | | 0-0 | 34-45-12 | D04681J | | 12 | | | D04781J | 39 | | 153-154 | |
| 228Z | | | | JC | 0-0 | 34-45-12 | D04681J | | 14 | | | D05827J | 3 | | 050-099, 150-152, 155-199, 277-299 | |
| 228Z | | | | JC | 0-0 | 34-45-12 | D04681J | | 14 | | | D04781J | 38 | | 153-154 | |
| 233B | 24 | PW | JH | | 6-0 | 23-22-15 | D04229J | | 17 | | | D04737J | 55 | | 050-099, 155-199, 277-299 | |
| 233B | 24 | PW | JH | | 5-0 | 23-22-15 | D04229J | | 17 | | | D04737J | 40 | | 150-152 | |
| 233B | 24 | PW | JH | | 4-0 | 23-22-15 | D04229J | | 17 | | | D04737J | 40 | | 153-154 | |
| 233B | 24 | PW | JH | | 4-0 | 23-22-15 | D04229J | | 17 | | | D04737J | 55 | | 275-276 | |
| 233R | 24 | PW | JH | | 0-0 | 23-22-15 | D04229J | | 16 | | | D04737J | 54 | | 050-099, 155-199, 275-299 | |
| 233R | 24 | PW | JH | | 0-0 | 23-22-15 | D04229J | | 16 | | | D04737J | 39 | | 150-154 | |
| 233Z | | | | JH | 0-0 | 23-22-15 | D04229J | | 18 | | | D04737J | 16 | | 050-099, 155-199, 275-299 | |
| 233Z | | | | JH | 0-0 | 23-22-15 | D04229J | | 18 | | | D04737J | 41 | | 150-154 | |
| 901B | 24 | PW | A | | 0-0 | 23-22-11 | D04811J | | 54 | | | D04953J | 19 | | 275-299 | |
| 901R | 24 | PW | A | | 10-0 | 23-22-11 | D04811J | | 53 | | | D04953J | 18 | | 275-299 | |
| 901Z | | | | A | 0-0 | 23-22-11 | D04811J | | 55 | | | D04953J | 20 | | 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W1630

Page 5 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|----|----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1645 | 286T1645 | | | INTERSHELF,R-AIDS | | | | | | | | | | | | |
| 001 | 24 | | PK | | 16-0 | SPARE | D04447J | | | | D04449J | | | | ALL | |
| 002 | 24 | | PK | | 16-0 | SPARE | D04447J | | | | D04449J | | | | ALL | |
| 003 | 22 | | PA | | 16-0 | SPARE | D04447J | | | | D04449J | | | | ALL | |
| 004 | 22 | | PA | | 16-0 | SPARE | D04447J | | | | D04449J | | | | ALL | |
| 006 | 24 | | PK | | 16-0 | 31-31-19 | D04447J | | | | D04449J | | | | ALL | |
| 007 | 24 | | PK | | 16-0 | 31-31-19 | D04447J | | | | D04449J | | | | ALL | |
| 201B | 24 | | PW | IA | 16-0 | SPARE | D04447J | | | | D04449J | | | | ALL | |
| 201R | 24 | | PW | IA | 0-0 | SPARE | D04447J | | | | D04449J | | | | ALL | |
| 201Z | | | | IA | 0-0 | SPARE | D04447J | | | | D04449J | | | | ALL | |
| 202B | 24 | | PW | IB | 16-0 | SPARE | D04447J | | | | D04449J | | | | ALL | |
| 202R | 24 | | PW | IB | 0-0 | SPARE | D04447J | | | | D04449J | | | | ALL | |
| 202Z | | | | IB | 0-0 | SPARE | D04447J | | | | D04449J | | | | ALL | |
| W1649 | 286T1649 | | | INTERSHELF E1-5,E2-3,E2-5 | | | | | | | | | | | | |
| 001 | 24 | | PK | | 4-0 | 31-31-17 | D04811J | | | | D04813J | | | | ALL | |
| 002 | 24 | | PK | | 4-0 | 31-31-17 | D04811J | | | | D04813J | | | | ALL | |
| 003 | 24 | | PK | | 4-0 | 31-31-17 | D04811J | | | | D04813J | | | | ALL | |
| 005 | 24 | | PK | | 4-0 | SPARE | D04811J | | | 15 | D04813J | | | | ALL | |
| 006 | 24 | | PK | | 4-0 | SPARE | D04811J | | | 16 | D04813J | | | | ALL | |
| 007 | 24 | | PV | AA | 4-0 | 23-51-12 | D04811J | | | 8 | D04813J | | | | ALL | |
| 007Z | | | | AA | 0-0 | 23-51-12 | D04811J | | | 9 | D04813J | | | | ALL | |
| 008 | 24 | | PV | AB | 18-0 | 23-51-13 | D05505J | | | 2 | D04813J | | | | 050-099 | |
| 008 | 24 | | PV | AB | 19-0 | 23-51-13 | D05505J | | | 2 | D04813J | | | | 150-199, 275-299 | |
| 008Z | | | | AB | 0-0 | 23-51-13 | D05505J | | | 3 | D04813J | | | | ALL | |
| 009 | 24 | | PK | | 4-0 | 31-51-33 | D04811J | | | 24 | D04813J | | | | ALL | |
| 010 | 24 | | PK | | 18-0 | SPARE | D04813J | | | 28 | D05505J | | | | 050-099 | |
| 010 | 24 | | PK | | 19-0 | SPARE | D04813J | | | 28 | D05505J | | | | 150-199, 275-299 | |
| 011 | 24 | | PK | | 4-0 | 31-31-17 | D04811J | | | 29 | D04813J | | | | ALL | |
| 012 | 24 | | PK | | 4-0 | 31-31-17 | D04811J | | | 30 | D04813J | | | | ALL | |
| 013 | 24 | | PK | | 4-0 | 23-21-11 | D04811J | | | 31 | D04813J | | | | ALL | |
| 014 | 24 | | PK | | 4-0 | 34-61-17 | D04811J | | | 43 | D04813J | | | | 157, 167-199, 277-299 | |
| 201B | 24 | | PW | IA | 4-0 | 23-51-12 | D04811J | | | 6 | D04813J | | | | ALL | |
| 201R | 24 | | PW | IA | 0-0 | 23-51-12 | D04811J | | | 5 | D04813J | | | | ALL | |
| 201Z | | | | IA | 0-0 | 23-51-12 | D04811J | | | 7 | D04813J | | | | ALL | |
| 202B | 24 | | PW | IB | 4-0 | 23-22-11 | D04811J | | | 23 | D04813J | | | | ALL | |
| 202R | 24 | | PW | IB | 0-0 | 23-22-11 | D04811J | | | 22 | D04813J | | | | ALL | |
| 202Z | | | | IB | 0-0 | 23-22-11 | D04811J | | | 41 | D04813J | | | | ALL | |
| 203B | 24 | | PW | IC | 4-0 | SPARE | D04811J | | | 13 | D04813J | | | | 150-199 | |
| 203R | 24 | | PW | IC | 0-0 | SPARE | D04811J | | | 4 | D04813J | | | | 150-199 | |

WIRE LIST

D280T132

91-21-11

Section W1640

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|----|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1649 | 286T1649 | | | INTERSHELF E1-5,E2-3,E2-5 (continued) | | | | | | | | | | | | | | |
| 203Z | | | | IC | 0-0 | SPARE | D04811J | | 14 | | | | D04813J | | 14 | | | 150-199 |
| 204B | 24 | | PW | ID | 4-0 | SPARE | D04811J | | 18 | | | | D04813J | | 18 | | | 050-099, 277-299 |
| 204B | 24 | | PW | ID | 4-0 | 31-31-14 | D04811J | | 18 | | | | D04813J | | 18 | | | 150-199, 275-276 |
| 204R | 24 | | PW | ID | 0-0 | SPARE | D04811J | | 17 | | | | D04813J | | 17 | | | 050-099, 277-299 |
| 204R | 24 | | PW | ID | 0-0 | 31-31-14 | D04811J | | 17 | | | | D04813J | | 17 | | | 150-199, 275-276 |
| 204Z | | | | ID | 0-0 | SPARE | D04811J | | | | ID | | D04813J | | | | IE | 050-099, 277-299 |
| 204Z | | | | ID | 0-0 | 31-31-14 | D04811J | | | | ID | | D04813J | | | | IE | 150-199, 275-276 |
| 205B | 24 | | PW | IE | 4-0 | SPARE | D04811J | | 20 | | | | D04813J | | 20 | | | 050-099, 277-299 |
| 205B | 24 | | PW | IE | 4-0 | 31-31-14 | D04811J | | 20 | | | | D04813J | | 20 | | | 150-199, 275-276 |
| 205R | 24 | | PW | IE | 0-0 | SPARE | D04811J | | 19 | | | | D04813J | | 19 | | | 050-099, 277-299 |
| 205R | 24 | | PW | IE | 0-0 | 31-31-14 | D04811J | | 19 | | | | D04813J | | 19 | | | 150-199, 275-276 |
| 205Z | | | | IE | 0-0 | SPARE | D04811J | | | | ID | | D04813J | | | | IE | 050-099, 277-299 |
| 205Z | | | | IE | 0-0 | 31-31-14 | D04811J | | | | ID | | D04813J | | | | IE | 150-199, 275-276 |
| 206B | 24 | | PW | IF | 4-0 | 23-22-11 | D04811J | | 26 | | | | D04813J | | 26 | | | ALL |
| 206R | 24 | | PW | IF | 0-0 | 23-22-11 | D04811J | | 25 | | | | D04813J | | 25 | | | ALL |
| 206Z | | | | IF | 0-0 | 23-22-11 | D04811J | | 27 | | | | D04813J | | 27 | | | ALL |
| 207B | 24 | | PW | IG | 4-0 | 34-61-25 | D04811J | | 33 | | | | D04813J | | 33 | | | ALL |
| 207R | 24 | | PW | IG | 0-0 | 34-61-25 | D04811J | | 32 | | | | D04813J | | 32 | | | ALL |
| 207Z | | | | IG | 0-0 | 34-61-25 | D04811J | | 34 | | | | D04813J | | 34 | | | ALL |
| 208B | 24 | | PW | IH | 4-0 | 34-61-25 | D04811J | | 36 | | | | D04813J | | 36 | | | ALL |
| 208R | 24 | | PW | IH | 0-0 | 34-61-25 | D04811J | | 35 | | | | D04813J | | 35 | | | ALL |
| 208Z | | | | IH | 0-0 | 34-61-25 | D04811J | | 37 | | | | D04813J | | 37 | | | ALL |
| 209B | 24 | | PW | II | 4-0 | 23-22-11 | D04811J | | 39 | | | | D04813J | | 39 | | | ALL |
| 209R | 24 | | PW | II | 0-0 | 23-22-11 | D04811J | | 38 | | | | D04813J | | 38 | | | ALL |
| 209Z | | | | II | 0-0 | 23-22-11 | D04811J | | 40 | | | | D04813J | | 40 | | | ALL |
| FRD | | | | | 0-0 | SPARE | D04811J | | | | ID | | D04811J | | 21 | | | 050-099, 277-299 |
| FRD | | | | | 0-0 | 31-31-14 | D04811J | | | | ID | | D04811J | | 21 | | | 150-199, 275-276 |
| FRE | | | | | 0-0 | SPARE | D04813J | | | | IE | | D04813J | | 21 | | | 050-099, 277-299 |
| FRE | | | | | 0-0 | 31-31-14 | D04813J | | | | IE | | D04813J | | 21 | | | 150-199, 275-276 |

WIRE LIST
D280T132

91-21-11
Section W1640
Page 2 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1661 | 286T1661 | | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | |
| 001 | 24 | | PK | | 27-0 | 23-32-13 | D02249 | | H | | D02233 | | 6 | | 150-199 |
| 002 | 24 | | PK | | 27-0 | 23-32-13 | D02249 | | E | | D02233 | | 7 | | 150-199 |
| 003 | 24 | | PK | | 27-0 | 23-32-13 | D02249 | | F | | D02233 | | 8 | | 150-199 |
| 004 | 20 | | PA | | 27-0 | 23-32-13 | D02249 | | M | | D02233 | | 2 | | 150-199 |
| 005 | 20 | | PA | | 27-0 | 23-32-13 | D02249 | | G | | D02233 | | 3 | | 150-199 |
| 006 | 20 | | PA | | 27-0 | 23-32-13 | D02249 | | J | | D02233 | | 5 | | 150-199 |
| 007 | 20 | | PA | | 27-0 | 23-32-11 | D02249 | | K | | D02233 | | 1 | | 150-199 |
| 008 | 20 | | PA | | 27-0 | 23-32-11 | D02249 | | L | | D02233 | | 4 | | 150-199 |
| 01CO | | | | A | 0-0 | 23-32-13 | D02251 | | = C1 | | D02231 | | = C1 | | 150-199 |
| 01CX | | | 5X | A | 27-0 | 23-32-13 | D02251 | | = A1 | | D02231 | | = A1 | | 150-199 |
| W1663 | 286T1663 | | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | |
| 001 | 24 | | PK | | 26-0 | 23-32-13 | D02253 | | H | | D02237 | | 6 | | 150-199 |
| 002 | 24 | | PK | | 26-0 | 23-32-13 | D02253 | | E | | D02237 | | 7 | | 150-199 |
| 003 | 24 | | PK | | 26-0 | 23-32-13 | D02253 | | F | | D02237 | | 8 | | 150-199 |
| 004 | 20 | | PA | | 26-0 | 23-32-13 | D02253 | | M | | D02237 | | 2 | | 150-199 |
| 005 | 20 | | PA | | 26-0 | 23-32-13 | D02253 | | G | | D02237 | | 3 | | 150-199 |
| 006 | 20 | | PA | | 26-0 | 23-32-13 | D02253 | | J | | D02237 | | 5 | | 150-199 |
| 007 | 20 | | PA | | 26-0 | 23-32-11 | D02253 | | K | | D02237 | | 1 | | 150-199 |
| 008 | 20 | | PA | | 26-0 | 23-32-11 | D02253 | | L | | D02237 | | 4 | | 150-199 |
| 01CO | | | | A | 0-0 | 23-32-13 | D02255 | | = C1 | | D02235 | | = C1 | | 150-199 |
| 01CX | | | 5X | A | 26-0 | 23-32-13 | D02255 | | = A1 | | D02235 | | = A1 | | 150-199 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|-----------------------------|-------|------|-------------|----------|---------|------|------|---------|-------|------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1700 | 286T1700 | EICAS-E8 TO P61 (LA) | | | | | | | | | | | | | | |
| 003 | 24 | | PK | 29-1 | 21-31-11 | D06200P | A03 | \$D | | D05400P | 3 | | | ALL | | |
| 004 | 24 | | PK | 29-1 | 28-41-13 | D06200P | A04 | \$D | | D05400P | 4 | | | ALL | | |
| 005 | 24 | | PV | AF | 29-1 | 80-11-11 | D06200P | A05 | \$D | D05400P | 5 | | | ALL | | |
| 005Z | | | AF | 0-0 | 80-11-11 | D06200P | DED | | | D05400P | DED | | | ALL | | |
| 006 | 24 | | PV | AG | 29-1 | 80-11-11 | D06200P | A06 | \$D | D05400P | 6 | | | ALL | | |
| 006Z | | | AG | 0-0 | 80-11-11 | D06200P | DED | | | D05400P | DED | | | ALL | | |
| 007 | 24 | | PK | 29-1 | 28-42-12 | D06200P | A07 | \$D | | D05400P | 7 | | | ALL | | |
| 011 | 24 | | PK | 29-1 | 36-11-11 | D06200P | A11 | \$D | | D05400P | 11 | | | ALL | | |
| 015 | 24 | | PK | 29-1 | 21-33-11 | D06200P | A15 | \$D | | D05400P | 15 | | | ALL | | |
| 016 | 24 | | PK | 29-1 | 74-31-11 | D06200P | A16 | \$D | | D05400P | 16 | | | ALL | | |
| 017 | 24 | | PK | 29-1 | 24-51-42 | D06200P | A17 | \$D | | D05400P | 17 | | | ALL | | |
| 018 | 24 | | PK | 29-1 | 24-11-11 | D06200P | A18 | \$D | | D05400P | 18 | | | ALL | | |
| 019 | 24 | | PK | 1-4 | SPARE | D06200P | A19 | \$D | | D06200P | CAP | Y | | ALL | | |
| 201B | 20 | | PB | AA | 29-1 | 21-65-11 | D05400P | 10 | | D06200P | A10 | \$D | | ALL | | |
| 201R | 20 | | PB | AA | 0-0 | 21-65-11 | D05400P | 9 | | D06200P | A09 | \$D | | ALL | | |
| 202B | 20 | | PB | AB | 29-1 | 21-65-11 | D05400P | 8 | | D06200P | A08 | \$D | | ALL | | |
| 202R | 20 | | PB | AB | 0-0 | 21-65-11 | D05400P | 2 | | D06200P | A02 | \$D | | ALL | | |
| 301B | 24 | | PM | MA | 29-1 | 21-64-11 | D06200P | A12 | \$D | D05400P | 12 | | | ALL | | |
| 301R | 24 | | PM | MA | 0-0 | 21-64-11 | D06200P | A13 | \$D | D05400P | 13 | | | ALL | | |
| 301Y | 24 | | PM | MA | 0-0 | 21-64-11 | D06200P | A14 | \$D | D05400P | 14 | | | ALL | | |
| W1701 | 286T1701 | E8 TO E2-3 SHELF | | | | | | | | | | | | | | |
| 001 | 24 | | PK | 26-0 | 22-14-31 | D05009P | A09 | \$D | | D05227J | 1 | | | ALL | | |
| 002 | 24 | | PK | 16-0 | 77-35-11 | D05009P | A10 | \$D | | D05247J | 14 | | | ALL | | |
| 003 | 24 | | PK | 15-0 | SPARE | D05011P | A12 | \$D | | D05247J | 1 | | | ALL | | |
| 004 | 24 | | PK | 15-0 | SPARE | D05011P | A13 | \$D | | D05247J | 2 | | | ALL | | |
| 005 | 24 | | PK | 16-0 | SPARE | D05009P | A11 | \$D | | D05247J | 3 | | | ALL | | |
| 006 | 24 | | PK | 16-0 | 22-34-11 | D05009P | A15 | \$D | | D05247J | 7 | | | ALL | | |
| 007 | 24 | | PK | 26-0 | 31-31-11 | D05009P | A19 | \$D | | D05227J | 3 | | | ALL | | |
| 008 | 24 | | PK | 26-0 | 31-51-41 | D05009P | B07 | \$D | | D05227J | 4 | | | ALL | | |
| 009 | 24 | | PK | 26-0 | 31-51-41 | D05009P | B08 | \$D | | D05227J | 5 | | | ALL | | |
| 010 | 24 | | PK | 26-0 | 31-51-41 | D05009P | B09 | \$D | | D05227J | 6 | | | ALL | | |
| 011 | 24 | | PK | 26-0 | 31-51-41 | D05009P | B10 | \$D | | D05227J | 7 | | | ALL | | |
| 012 | 24 | | PK | 26-0 | 31-51-42 | D05009P | B11 | \$D | | D05227J | 11 | | | ALL | | |
| 013 | 24 | | PK | 26-0 | 34-16-11 | D05009P | B12 | \$D | | D05227J | 12 | | | ALL | | |
| 014 | 24 | | PK | 16-0 | 34-21-11 | D05009P | B13 | \$D | | D05247J | 11 | | | ALL | | |
| 015 | 24 | | PK | 16-0 | 34-21-11 | D05009P | B14 | \$D | | D05247J | 12 | | | ALL | | |
| 016 | 24 | | PK | 16-0 | 34-21-11 | D05009P | B15 | \$D | | D05247J | 13 | | | ALL | | |
| 017 | 24 | | PK | 26-0 | 34-46-12 | D05009P | B19 | \$D | | D05227J | 13 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W1700

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1701 | 286T1701 | | | E8 TO E2-3 SHELF (continued) | | | | | | | | | | | |
| 018 | 24 | | PK | | 25-0 | SPARE | D05011P | A10 | \$D | | D05227J | REF | JW | | ALL |
| 019 | 24 | | PK | | 25-0 | SPARE | D05011P | A11 | \$D | | D05227J | 15 | | | ALL |
| 020 | 24 | | PK | | 26-0 | 31-31-13 | D05009P | B05 | \$D | | D05227J | 16 | | | ALL |
| 021 | 24 | | PK | | 25-0 | 34-61-15 | D05011P | A08 | \$D | | D05227J | 23 | | | ALL |
| 022 | 24 | | PK | | 26-0 | 31-41-16 | D05009P | A02 | \$D | | D05227J | 24 | | | ALL |
| 023 | 24 | | PK | | 26-0 | 31-51-41 | D05009P | B06 | \$D | | D05227J | 28 | | | ALL |
| 024 | 24 | | PK | | 25-0 | 34-53-11 | D05011P | A09 | \$D | | D05227J | 29 | | | ALL |
| 025 | 24 | | PK | | 25-0 | 22-14-31 | D05011P | A14 | \$D | | D05227J | 2 | | | ALL |
| 026 | 24 | | PK | | 27-0 | 34-12-62 | D05011P | A15 | \$D | | D05227J | 14 | | | ALL |
| 027 | 24 | | PK | | 15-0 | 34-12-12 | D05011P | A16 | \$D | | D05247J | 29 | | | ALL |
| 028 | 24 | | PK | | 25-0 | 31-41-16 | D05011P | A17 | \$D | | D05227J | 30 | | | ALL |
| 029 | 24 | | PK | | 25-0 | 34-22-38 | D05011P | A18 | \$D | | D05227J | 31 | | | ALL |
| 030 | 24 | | PK | | 25-0 | 31-51-43 | D05011P | A19 | \$D | | D05227J | 32 | | | ALL |
| 031 | 24 | | PK | | 1-0 | SPARE | D05011P | B02 | \$D | | D05011P | CAP | Y | | ALL |
| 032 | 24 | | PK | | 1-0 | SPARE | D05011P | B03 | \$D | | D05011P | CAP | Y | | ALL |
| 033 | 24 | | PK | | 1-0 | SPARE | D05011P | B04 | \$D | | D05011P | CAP | Y | | ALL |
| 034 | 24 | | PK | | 1-0 | SPARE | D05011P | B05 | \$D | | D05011P | CAP | Y | | ALL |
| 035 | 24 | | PK | | 1-0 | SPARE | D05011P | B06 | \$D | | D05011P | CAP | Y | | ALL |
| 036 | 24 | | PK | | 1-0 | SPARE | D05011P | B07 | \$D | | D05011P | CAP | Y | | ALL |
| 037 | 24 | | PK | | 1-0 | SPARE | D05011P | B08 | \$D | | D05011P | CAP | Y | | ALL |
| 038 | 24 | | PK | | 1-0 | SPARE | D05011P | B09 | \$D | | D05011P | CAP | Y | | ALL |
| 039 | 24 | | PK | | 1-0 | SPARE | D05011P | B10 | \$D | | D05011P | CAP | Y | | ALL |
| 040 | 24 | | PK | | 1-0 | SPARE | D05011P | B11 | \$D | | D05011P | CAP | Y | | ALL |
| 041 | 24 | | PK | | 1-0 | SPARE | D05011P | B12 | \$D | | D05011P | CAP | Y | | ALL |
| 042 | 24 | | PK | | 1-0 | SPARE | D05011P | B13 | \$D | | D05011P | CAP | Y | | ALL |
| 043 | 24 | | PK | | 1-0 | SPARE | D05011P | B14 | \$D | | D05011P | CAP | Y | | ALL |
| 044 | 24 | | PK | | 1-0 | SPARE | D05011P | B15 | \$D | | D05011P | CAP | Y | | ALL |
| 045 | 24 | | PK | | 1-0 | SPARE | D05011P | B16 | \$D | | D05011P | CAP | Y | | ALL |
| 046 | 24 | | PK | | 1-0 | SPARE | D05011P | B17 | \$D | | D05011P | CAP | Y | | ALL |
| 047 | 24 | | PK | | 1-0 | SPARE | D05011P | B18 | \$D | | D05011P | CAP | Y | | ALL |
| 048 | 24 | | PK | | 1-0 | SPARE | D05011P | B19 | \$D | | D05011P | CAP | Y | | ALL |
| 049 | 24 | | PK | | 8-0 | 27-48-11 | D05247J | 37 | | | SP00583 | 9 | | | 157, 167-199, 277-299 |
| 051 | 22 | | PA | | 18-0 | 31-31-25 | D05247J | 21 | | | D05227J | 47 | | | 050-099, 150-199 |
| 052 | 22 | | PA | | 18-0 | 31-31-25 | D05247J | 24 | | | D05227J | 50 | | | 050-099, 150-199 |
| 053 | 22 | | PA | | 18-0 | 31-31-25 | D05247J | 36 | | | D05227J | 53 | | | 050-099, 150-199 |
| 054 | 24 | | PK | | 8-0 | 27-48-11 | D05247J | 38 | | | SP00581 | 9 | | | 157, 167-199, 277-299 |
| 201B | 24 | | PW | IA | 16-0 | 22-32-12 | D05009P | A13 | \$D | | D05247J | 5 | | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 22-32-12 | D05009P | A12 | \$D | | D05247J | 4 | | | ALL |
| 201Z | | | | IA | 0-0 | 22-32-12 | D05009P | A14 | \$D | | D05247J | 6 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W1700
 Page 2
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1701 | 286T1701 | | | E8 TO E2-3 SHELF (continued) | | | | | | | | | | | | |
| 202B | 24 | PW | IB | 16-0 | 22-41-13 | D05009P | A17 | \$D | | D05247J | 9 | | | ALL | | |
| 202R | 24 | PW | IB | 0-0 | 22-41-13 | D05009P | A16 | \$D | | D05247J | 8 | | | ALL | | |
| 202Z | | | IB | 0-0 | 22-41-13 | D05009P | A18 | \$D | | D05247J | 10 | | | ALL | | |
| 203B | 24 | PW | IC | 26-0 | 31-31-13 | D05009P | B03 | \$D | | D05227J | 9 | | | ALL | | |
| 203R | 24 | PW | IC | 0-0 | 31-31-13 | D05009P | B02 | \$D | | D05227J | 8 | | | ALL | | |
| 203Z | | | IC | 0-0 | 31-31-13 | D05009P | B04 | \$D | | D05227J | 10 | | | ALL | | |
| 204B | 24 | PW | ID | 25-0 | 34-61-14 | D05011P | A03 | \$D | | D05227J | 18 | | | ALL | | |
| 204R | 24 | PW | ID | 0-0 | 34-61-14 | D05011P | A02 | \$D | | D05227J | 17 | | | ALL | | |
| 204Z | | | ID | 0-0 | 34-61-14 | D05011P | A04 | \$D | | D05227J | 19 | | | ALL | | |
| 205B | 24 | PW | IE | 25-0 | 34-61-15 | D05011P | A06 | \$D | | D05227J | 21 | | | ALL | | |
| 205R | 24 | PW | IE | 0-0 | 34-61-15 | D05011P | A05 | \$D | | D05227J | 20 | | | ALL | | |
| 205Z | | | IE | 0-0 | 34-61-15 | D05011P | A07 | \$D | | D05227J | 22 | | | ALL | | |
| 206B | 24 | PW | IF | 16-0 | 31-41-31 | D05009P | A04 | \$D | | D05247J | 16 | | | ALL | | |
| 206R | 24 | PW | IF | 0-0 | 31-41-31 | D05009P | A03 | \$D | | D05247J | 15 | | | ALL | | |
| 206Z | | | IF | 0-0 | 31-41-31 | D05009P | A05 | \$D | | D05247J | 17 | | | ALL | | |
| 207B | 24 | PW | IG | 16-0 | 31-41-31 | D05009P | A07 | \$D | | D05247J | 19 | | | ALL | | |
| 207R | 24 | PW | IG | 0-0 | 31-41-31 | D05009P | A06 | \$D | | D05247J | 18 | | | ALL | | |
| 207Z | | | IG | 0-0 | 31-41-31 | D05009P | A08 | \$D | | D05247J | 20 | | | ALL | | |
| 208B | 24 | PW | IH | 26-0 | SPARE | D05009P | B18 | \$D | | D05227J | 26 | | | ALL | | |
| 208R | 24 | PW | IH | 0-0 | SPARE | D05009P | B17 | \$D | | D05227J | 25 | | | ALL | | |
| 208Z | | | IH | 0-0 | SPARE | D05009P | B16 | \$D | | D05227J | 27 | | | ALL | | |
| 210B | 24 | PW | IJ | 18-0 | 31-31-20 | D05247J | 31 | | | D05227J | 37 | | | ALL | | |
| 210R | 24 | PW | IJ | 0-0 | 31-31-20 | D05247J | 30 | | | D05227J | 36 | | | ALL | | |
| 210Z | | | IJ | 0-0 | 31-31-20 | D05247J | 32 | | | D05227J | 38 | | | ALL | | |
| 211B | 24 | PW | IK | 18-0 | 31-31-20 | D05247J | 34 | | | D05227J | 34 | | | ALL | | |
| 211R | 24 | PW | IK | 0-0 | 31-31-20 | D05247J | 33 | | | D05227J | 33 | | | ALL | | |
| 211Z | | | IK | 0-0 | 31-31-20 | D05247J | 35 | | | D05227J | 35 | | | ALL | | |
| 212B | 22 | PB | IL | 18-0 | 31-31-25 | D05247J | 23 | | | D05227J | 49 | | | 050-099, 150-199 | | |
| 212R | 22 | PB | IL | 0-0 | 31-31-25 | D05247J | 22 | | | D05227J | 48 | | | 050-099, 150-199 | | |
| 213B | 22 | PB | IM | 18-0 | 31-31-25 | D05247J | 26 | | | D05227J | 52 | | | 050-099, 150-199 | | |
| 213R | 22 | PB | IM | 0-0 | 31-31-25 | D05247J | 25 | | | D05227J | 51 | | | 050-099, 150-199 | | |
| 214B | 22 | PB | IN | 18-0 | 31-31-25 | D05247J | 28 | | | D05227J | 55 | | | 050-099, 150-199 | | |
| 214R | 22 | PB | IN | 0-0 | 31-31-25 | D05247J | 27 | | | D05227J | 54 | | | 050-099, 150-199 | | |
| W1702 | 286T1702 | | | EICAS-E8 TO P36 | | | | | | | | | | | | |
| 002 | 24 | PK | | 11-0 | 21-25-11 | D06202P | A02 | \$D | | D05360P | 2 | | | ALL | | |
| 003 | 24 | PK | | 11-0 | 27-18-11 | D06202P | A03 | \$D | | D05360P | 3 | | | 050-099, 150-154, 162-165, 275-276 | | |

WIRE LIST
D280T132

91-21-11
Section W1700
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1702 | 286T1702 | | | EICAS-E8 TO P36 (continued) | | | | | | | | | | | |
| 004 | 24 | | PK | | 11-0 | 27-18-11 | D06202P | A04 | \$D | | D05360P | | 4 | | 050-099, 150-154, 162-165, 275-276 |
| 005 | 24 | | PK | | 11-0 | 27-13-11 | D06202P | A05 | \$D | | D05360P | | 5 | | ALL |
| 006 | 24 | | PK | | 11-0 | 30-21-11 | D06202P | A06 | \$D | | D05360P | | 6 | | ALL |
| 007 | 24 | | PK | | 11-0 | 27-18-11 | D06202P | A07 | \$D | | D05360P | | 7 | | 050-099, 150-156, 162-166, 275-276 |
| 007 | 24 | | PK | | 11-0 | SPARE | D06202P | A07 | \$D | | D05360P | | 7 | | 157, 167-199, 277-299 |
| 008 | 24 | | PK | | 11-0 | 27-18-11 | D06202P | A08 | \$D | | D05360P | | 8 | | 050-099, 150-156, 162-166, 275-276 |
| 008 | 24 | | PK | | 11-0 | SPARE | D06202P | A08 | \$D | | D05360P | | 8 | | 157, 167-199, 277-299 |
| 009 | 24 | | PK | | 11-0 | 21-58-16 | D06202P | A09 | \$D | | D05360P | | 9 | | ALL |
| 011 | 24 | | PK | | 11-0 | 28-42-11 | D06202P | A11 | \$D | | D05360P | | 11 | | ALL |
| 013 | 24 | | PK | | 11-0 | 24-11-11 | D06202P | A13 | \$D | | D05360P | | 13 | | ALL |
| 014 | 24 | | PK | | 11-0 | 27-23-11 | D06202P | A14 | \$D | | D05360P | | 14 | | ALL |
| 015 | 24 | | PK | | 11-0 | 78-36-11 | D06202P | A15 | \$D | | D05360P | | 15 | | ALL |
| 016 | 24 | | PK | | 11-0 | 30-21-11 | D06202P | A16 | \$D | | D05360P | | 16 | | ALL |
| 017 | 24 | | PK | | 11-0 | 29-32-11 | D06202P | A17 | \$D | | D05360P | | 17 | | ALL |
| 018 | 24 | | PK | | 11-0 | 29-32-11 | D06202P | A18 | \$D | | D05360P | | 18 | | ALL |
| 019 | 24 | | PK | | 11-0 | 79-35-11 | D06202P | A19 | \$D | | D05360P | | 19 | | ALL |
| 025 | 24 | | PK | | 11-0 | 75-23-11 | D06202P | B05 | \$D | | D05360P | | 25 | | ALL |
| 026 | 24 | | PK | | 11-0 | SPARE | D06202P | B06 | \$D | | D05360P | | 26 | | 275-299 |
| 027 | 24 | | PK | | 11-0 | SPARE | D06202P | B07 | \$D | | D05360P | | 27 | | 275-299 |
| 028 | 24 | | PK | | 12-0 | 30-21-11 | D06202P | B08 | \$D | | D05360P | | 20 | | 050-099, 150-154 |
| 028 | 24 | | PK | | 11-0 | 30-21-11 | D06202P | B08 | \$D | | D05360P | | 20 | | 155-199 |
| 029 | 24 | | PK | | 2-0 | SPARE | D06202P | B09 | \$D | | D06202P | CAP | Y | | 150-199 |
| 033 | 24 | | PK | | 11-0 | 32-09-11 | D06202P | B13 | \$D | | D05360P | | 33 | | ALL |
| 034 | 24 | | PK | | 11-0 | 32-09-11 | D06202P | B14 | \$D | | D05360P | | 34 | | ALL |
| 035 | 24 | | PK | | 11-0 | 27-28-11 | D06202P | B15 | \$D | | D05360P | | 35 | | 050-099, 150-154, 162-165, 275-276 |
| 035 | 24 | | PK | | 11-0 | 27-28-11 | D06202P | B15 | \$D | | SM00564 | | | S | 155-157, 166-199, 277-299 |
| 036 | 24 | | PK | | 11-0 | 27-28-11 | D06202P | B16 | \$D | | D05360P | | 36 | | 050-099, 150-154, 162-165, 275-276 |
| 036 | 24 | | PK | | 11-0 | 27-28-11 | D06202P | B16 | \$D | | SM00566 | | | S | 155-157, 166-199, 277-299 |
| 037 | 24 | | PK | | 11-0 | 21-43-11 | D06202P | B17 | \$D | | D05360P | | 37 | | ALL |
| 038 | 24 | | PK | | 11-0 | 21-44-11 | D06202P | B18 | \$D | | D05360P | | 38 | | ALL |
| 039 | 24 | | PK | | 11-0 | 27-31-11 | D06202P | B19 | \$D | | D05360P | | 39 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1700

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1702 | 286T1702 | | | EICAS-E8 TO P36 (continued) | | | | | | | | | | | | | |
| 040 | 24 | | PK | 1-0 | 27-28-11 | D05360P | | 35 | | | | | SM00564 | | S | | 155-157, 166-199, 277-299 |
| 042 | 24 | | PK | 12-0 | 27-38-11 | D06208P | A02 | \$D | | | | | D05360P | 42 | | | 050-099, 150-154, 162-165, 275-276 |
| 042 | 24 | | PK | 12-0 | 27-38-11 | D06208P | A02 | \$D | | | | | SM00006 | | S | | 155-157, 166-199, 277-299 |
| 043 | 24 | | PK | 12-0 | 27-38-11 | D06208P | A03 | \$D | | | | | D05360P | 43 | | | 050-099, 150-154, 162-165, 275-276 |
| 043 | 24 | | PK | 12-0 | 27-38-11 | D06208P | A03 | \$D | | | | | SM00008 | | S | | 155-157, 166-199, 277-299 |
| 044 | 24 | | PK | 12-0 | 27-38-11 | D06208P | A04 | \$D | | | | | D05360P | 44 | | | 050-099, 150-154, 162-165, 275-276 |
| 044 | 24 | | PK | 12-0 | 27-38-11 | D06208P | A04 | \$D | | | | | SM00002 | | S | | 155-157, 166-199, 277-299 |
| 045 | 24 | | PK | 12-0 | 27-38-11 | D06208P | A05 | \$D | | | | | D05360P | 45 | | | 050-099, 150-154, 162-165, 275-276 |
| 045 | 24 | | PK | 12-0 | 27-38-11 | D06208P | A05 | \$D | | | | | SM00004 | | S | | 155-157, 166-199, 277-299 |
| 046 | 24 | | PK | 12-0 | 28-22-21 | D06208P | A06 | \$D | | | | | D05360P | 46 | | | ALL |
| 047 | 24 | | PK | 12-0 | 77-35-11 | D06208P | A07 | \$D | | | | | D05360P | 47 | | | ALL |
| 048 | 24 | | PK | 12-0 | 73-33-11 | D06208P | A08 | \$D | | | | | D05360P | 48 | | | ALL |
| 051 | 24 | | PK | 12-0 | 79-33-11 | D06208P | A11 | \$D | | | | | D05360P | 51 | | | ALL |
| 052 | 24 | | PK | 12-0 | 29-32-11 | D06208P | A12 | \$D | | | | | D05360P | 52 | | | ALL |
| 053 | 24 | | PK | 1-0 | SPARE | D06208P | A13 | \$D | | | | | D06208P | CAP | Y | | ALL |
| 054 | 24 | | PK | 1-0 | SPARE | D06208P | A14 | \$D | | | | | D06208P | CAP | Y | | ALL |
| 059 | 24 | | PK | 1-0 | SPARE | D06208P | A19 | \$D | | | | | D06208P | CAP | Y | | ALL |
| 060 | 24 | | PK | 1-0 | 27-28-11 | D05360P | | 36 | | | | | SM00566 | | S | | 155-157, 166-199, 277-299 |
| 061 | 24 | | PK | 12-0 | 27-28-11 | D06980P | | 3 | | | | | D05360P | 1 | | | 155-157, 166-199, 277-299 |
| 062 | 24 | | PK | 13-0 | 27-38-11 | D06980P | | 7 | | | | | D05360P | 3 | | | 155-157, 166-199, 277-299 |
| 063 | 24 | | PK | 13-0 | 27-38-11 | D06980P | | 8 | | | | | SM00006 | | S | | 155-157, 166-199, 277-299 |
| 064 | 24 | | PK | 13-0 | 27-38-11 | D06980P | | 9 | | | | | SM00008 | | S | | 155-157, 166-199, 277-299 |
| 065 | 24 | | PK | 13-0 | 27-28-11 | D06980P | | 1 | | | | | SM00564 | | S | | 155-157, 166-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W1700

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|-----|-----|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1702 | 286T1702 | | | EICAS-E8 TO P36 (continued) | | | | | | | | | | | | | | |
| 066 | 24 | | PK | | 13-0 | 27-28-11 | D06980P | | | | 2 | | | | SM00566 | S | | 155-157, 166-199, 277-299 |
| 067 | 24 | | PK | | 1-0 | 27-38-11 | D05360P | | | | 42 | | | | SM00006 | S | | 155-157, 166-199, 277-299 |
| 068 | 24 | | PK | | 1-0 | 27-38-11 | D05360P | | | | 43 | | | | SM00008 | S | | 155-157, 166-199, 277-299 |
| 069 | 24 | | PK | | 1-0 | 27-38-11 | D05360P | | | | 44 | | | | SM00002 | S | | 155-157, 166-199, 277-299 |
| 070 | 24 | | PK | | 1-0 | 27-38-11 | D05360P | | | | 45 | | | | SM00004 | S | | 155-157, 166-199, 277-299 |
| 071 | 24 | | PK | | 13-0 | 27-38-11 | D06980P | | | | 4 | | | | D05360P | 4 | | 155-157, 166-199, 277-299 |
| 072 | 24 | | PK | | 13-0 | 27-38-11 | D06980P | | | | 5 | | | | SM00002 | S | | 155-157, 166-199, 277-299 |
| 073 | 24 | | PK | | 13-0 | 27-38-11 | D06980P | | | | 6 | | | | SM00004 | S | | 155-157, 166-199, 277-299 |
| 095 | 24 | | PK | | 13-0 | 27-48-11 | D06980P | | | | 10 | | | | SP00581 | 9 | | 157, 167-199, 277-299 |
| 096 | 24 | | PK | | 13-0 | 27-48-11 | D06980P | | | | 11 | | | | SP00583 | 9 | | 157, 167-199, 277-299 |
| 201B | 24 | | PW | IA | 11-0 | 73-21-14 | D06202P | | B02 | \$D | | | | | D05360P | 28 | | ALL |
| 201R | 24 | | PW | IA | 0-0 | 73-21-14 | D06202P | | B03 | \$D | | | | | D05360P | 29 | | ALL |
| 201Z | | | | IA | 0-0 | 73-21-14 | D06202P | | B04 | \$D | | | | | D05360P | 53 | | ALL |
| 202B | 24 | | PL | IB | 11-0 | 21-44-22 | D06202P | | B06 | \$D | | | | | D05360P | 26 | | 050-099, 150-199 |
| 202R | 24 | | PL | IB | 0-0 | 21-44-22 | D06202P | | B07 | \$D | | | | | D05360P | 27 | | 050-099, 150-199 |
| 203B | 24 | | PL | IC | 1-0 | SPARE | D06202P | | B08 | \$D | | | | | D06202P | CAP | Y | 275-299 |
| 203R | 24 | | PL | IC | 0-0 | SPARE | D06202P | | B09 | \$D | | | | | D06202P | CAP | Y | 275-299 |
| 204B | 24 | | PL | ID | 12-0 | 36-22-21 | D06208P | | A09 | \$D | | | | | D05360P | 49 | | ALL |
| 204R | 24 | | PL | ID | 0-0 | 36-22-21 | D06208P | | A10 | \$D | | | | | D05360P | 50 | | ALL |
| 205B | 24 | | PL | AB | 11-0 | 29-31-11 | D05360P | | | | 10 | | | | D06202P | A10 | \$D | ALL |
| 205R | 24 | | PL | AB | 0-0 | 29-31-11 | D05360P | | | | 12 | | | | D06202P | A12 | \$D | ALL |
| 206B | 24 | | PW | IF | 12-0 | 77-12-12 | D06208P | | A16 | \$D | | | | | D05360P | 55 | | 050-099 |
| 206B | 24 | | PW | AD | 12-0 | 77-12-12 | D06208P | | A16 | \$D | | | | | D05360P | 55 | | 150-199, 275-299 |
| 206R | 24 | | PW | IF | 0-0 | 77-12-12 | D06208P | | A17 | \$D | | | | | D05360P | 54 | | 050-099 |
| 206R | 24 | | PW | AD | 0-0 | 77-12-12 | D06208P | | A17 | \$D | | | | | D05360P | 54 | | 150-199, 275-299 |
| 206Z | | | | IF | 0-0 | 77-12-12 | D06208P | | | | | | | FA | D05360P | 40 | | 050-099 |
| 206Z | | | | AD | 0-0 | 77-12-12 | D06208P | | | | | | | FA | D05360P | 40 | | 150-199, 275-299 |
| 301B | 24 | | PM | MA | 11-0 | 79-31-11 | D06202P | | B11 | \$D | | | | | D05360P | 31 | | ALL |
| 301R | 24 | | PM | MA | 0-0 | 79-31-11 | D06202P | | B10 | \$D | | | | | D05360P | 30 | | ALL |
| 301Y | 24 | | PM | MA | 0-0 | 79-31-11 | D06202P | | B12 | \$D | | | | | D05360P | 32 | | ALL |
| FRA | | | | | 0-0 | 77-12-12 | D06208P | | | | | | | FA | D06208P | A18 | \$D | 050-099, 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1700

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|-------------|----|------------------------------------|-------------|----------|---------|------|------|--------|---------|---------|------|--------|------------------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1702 | 286T1702 | | | EICAS-E8 TO P36 (continued) | | | | | | | | | | | | |
| FRA | | | | | 12-0 | 77-12-12 | D06208P | | | | FA | D06208P | A18 | \$D | 150-199 | |
| FRB | | | | | 0-0 | 77-12-12 | D06208P | | | | FA | D06208P | A15 | \$D | 050-099, 275-299 | |
| FRB | | | | | 12-0 | 77-12-12 | D06208P | | | | FA | D06208P | A15 | \$D | 150-199 | |
| W1703 | 286T1703 | | | E8 TO E2-3 SHELF | | | | | | | | | | | | |
| 001 | 24 | | PK | | 27-7 | 22-21-21 | D05063P | A09 | \$D | | D05065J | | 1 | | ALL | |
| 002 | 24 | | PK | | 27-7 | 27-09-14 | D05063P | A11 | \$D | | D05065J | | 2 | | ALL | |
| 003 | 24 | | PK | | 27-7 | SPARE | D05063P | A10 | \$D | | D05065J | | 3 | | ALL | |
| 004 | 24 | | PK | | 27-7 | 27-09-14 | D05063P | A13 | \$D | | D05065J | | 4 | | ALL | |
| 005 | 24 | | PK | | 27-7 | 34-21-21 | D05063P | A18 | \$D | | D05065J | | 5 | | ALL | |
| 006 | 24 | | PK | | 27-7 | 34-21-21 | D05063P | A17 | \$D | | D05065J | | 6 | | ALL | |
| 007 | 24 | | PK | | 27-7 | 34-21-21 | D05063P | A16 | \$D | | D05065J | | 7 | | ALL | |
| 008 | 24 | | PK | | 27-7 | 34-61-25 | D05063P | B03 | \$D | | D05065J | | 8 | | ALL | |
| 009 | 24 | | PK | | 27-7 | 27-09-14 | D05063P | B07 | \$D | | D05065J | | 9 | | ALL | |
| 010 | 24 | | PK | | 27-7 | 34-61-16 | D05063P | B08 | \$D | | D05065J | | 10 | | ALL | |
| 011 | 24 | | PK | | 27-7 | 31-51-11 | D05063P | A14 | \$D | | D05065J | | 11 | | ALL | |
| 012 | 24 | | PK | | 27-7 | 34-61-25 | D05063P | B02 | \$D | | D05065J | | 12 | | ALL | |
| 013 | 24 | | PK | | 27-7 | 27-09-14 | D05063P | A12 | \$D | | D05065J | | 13 | | ALL | |
| 014 | 24 | | PK | | 27-7 | 31-51-41 | D05063P | A15 | \$D | | D05065J | | 14 | | ALL | |
| 015 | 24 | | PK | | 27-7 | SPARE | D05063P | B19 | \$D | | D05065J | | 25 | | ALL | |
| 016 | 24 | | PK | | 27-7 | 34-12-22 | D05063P | A02 | \$D | | D05065J | | 29 | | ALL | |
| 017 | 24 | | PK | | 0-7 | SPARE | D05063P | A19 | \$D | | D05063P | CAP | Y | | ALL | |
| 018 | 24 | | PK | | 27-7 | 31-41-16 | D05063P | B13 | \$D | | D05065J | | 30 | | ALL | |
| 019 | 24 | | PK | | 27-7 | 31-41-16 | D05063P | B14 | \$D | | D05065J | | 31 | | ALL | |
| 020 | 24 | | PK | | 0-7 | SPARE | D05063P | B15 | \$D | | D05063P | CAP | Y | | 275-276 | |
| 021 | 24 | | PK | | 0-7 | SPARE | D05063P | B16 | \$D | | D05063P | CAP | Y | | ALL | |
| 022 | 24 | | PK | | 0-7 | SPARE | D05063P | B17 | \$D | | D05063P | CAP | Y | | ALL | |
| 023 | 24 | | PK | | 0-7 | SPARE | D05063P | B18 | \$D | | D05063P | CAP | Y | | ALL | |
| 025 | 24 | | PK | | 27-7 | 34-45-13 | D05063P | B15 | \$D | | D05065J | | 15 | | 050-099, 150-199, 277-299 | |
| 201B | 24 | | PW | IA | 27-7 | 34-61-25 | D05063P | B05 | \$D | | D05065J | | 23 | | ALL | |
| 201R | 24 | | PW | IA | 0-0 | 34-61-25 | D05063P | B04 | \$D | | D05065J | | 22 | | ALL | |
| 201Z | | | | IA | 0-0 | 34-61-25 | D05063P | B06 | \$D | | D05065J | | 24 | | ALL | |
| 202B | 24 | | PW | IB | 27-7 | 31-41-33 | D05063P | A04 | \$D | | D05065J | | 17 | | ALL | |
| 202R | 24 | | PW | IB | 0-0 | 31-41-33 | D05063P | A03 | \$D | | D05065J | | 16 | | ALL | |
| 202Z | | | | IB | 0-0 | 31-41-33 | D05063P | A05 | \$D | | D05065J | | 18 | | ALL | |
| 203B | 24 | | PW | IC | 27-7 | 31-41-33 | D05063P | A07 | \$D | | D05065J | | 20 | | ALL | |
| 203R | 24 | | PW | IC | 0-0 | 31-41-33 | D05063P | A06 | \$D | | D05065J | | 19 | | ALL | |
| 203Z | | | | IC | 0-0 | 31-41-33 | D05063P | A08 | \$D | | D05065J | | 21 | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1700

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1703 | 286T1703 | | | E8 TO E2-3 SHELF (continued) | | | | | | | | | | | |
| 204B | 24 | PW | ID | | 27-7 | 34-61-24 | D05063P | B11 | \$D | | D05065J | 27 | | | ALL |
| 204R | 24 | PW | ID | | 0-0 | 34-61-24 | D05063P | B10 | \$D | | D05065J | 26 | | | ALL |
| 204Z | | | ID | | 0-0 | 34-61-24 | D05063P | | | FD | D05065J | 28 | | | ALL |
| FR4 | | | | | 0-0 | 34-61-24 | D05063P | | | FD | D05063P | B12 | | | ALL |
| FRD | | | | | 0-0 | 34-61-24 | D05063P | | | FD | D05063P | B09 | | | ALL |
| W1704 | 286T1704 | | | EICAS-E8 TO P54,P37,P33 | | | | | | | | | | | |
| 002 | 24 | PK | | | 27-0 | 78-36-11 | D06204P | A02 | \$D | | D05372P | 2 | | | ALL |
| 003 | 24 | PK | | | 27-0 | 27-18-11 | D06204P | A03 | \$D | | D05372P | 3 | | | 050-099, 150-156, 162-166, 275-276 |
| 003 | 24 | PK | | | 27-0 | SPARE | D06204P | A03 | \$D | | D05372P | 3 | | | 157, 167-199, 277-299 |
| 004 | 24 | PK | | | 27-0 | 27-18-11 | D06204P | A04 | \$D | | D05372P | 4 | | | 050-099, 150-156, 162-166, 275-276 |
| 004 | 24 | PK | | | 27-0 | SPARE | D06204P | A04 | \$D | | D05372P | 4 | | | 157, 167-199, 277-299 |
| 005 | 24 | PK | | | 27-0 | 28-42-12 | D06204P | A05 | \$D | | D05372P | 5 | | | ALL |
| 006 | 24 | PK | | | 27-0 | 27-51-61 | D06204P | A06 | \$D | | D05372P | 6 | | | ALL |
| 007 | 24 | PK | | | 27-0 | 27-18-11 | D06204P | A07 | \$D | | D05372P | 7 | | | 050-099, 150-156, 162-166, 275-276 |
| 007 | 24 | PK | | | 27-0 | SPARE | D06204P | A07 | \$D | | D05372P | 7 | | | 157, 167-199, 277-299 |
| 008 | 24 | PK | | | 27-0 | 27-18-11 | D06204P | A08 | \$D | | D05372P | 8 | | | 050-099, 150-156, 162-166, 275-276 |
| 008 | 24 | PK | | | 27-0 | SPARE | D06204P | A08 | \$D | | D05372P | 8 | | | 157, 167-199, 277-299 |
| 009 | 22 | PA | | | 20-0 | 30-81-11 | D06204P | A09 | \$D | | D05332P | 18 | | | 050-099 |
| 009 | 22 | PA | | | 27-0 | 30-81-11 | D06204P | A09 | \$D | | D05332P | 18 | | | 150-199 |
| 009 | 24 | PK | | | 27-0 | SPARE | D06204P | A09 | \$D | | D05372P | 9 | | | 275-299 |
| 010 | 22 | PA | | | 20-0 | 30-81-11 | D06204P | A10 | \$D | | D05332P | 19 | | | 050-099 |
| 010 | 22 | PA | | | 27-0 | 30-81-11 | D06204P | A10 | \$D | | D05332P | 19 | | | 150-199 |
| 010 | 24 | PK | | | 27-0 | SPARE | D06204P | A10 | \$D | | D05372P | 10 | | | 275-299 |
| 011 | 24 | PK | | | 27-0 | 28-42-11 | D06204P | A11 | \$D | | D05372P | 11 | | | ALL |
| 012 | 24 | PK | | | 27-0 | 78-36-21 | D06204P | A12 | \$D | | D05372P | 12 | | | ALL |
| 013R | 22 | PH | | | 44-1 | 26-18-11 | D06204P | A13 | \$D | | D05540P | 3 | | | 050-099, 275-299 |
| 013R | 22 | PA | | | 44-1 | 26-18-11 | D06204P | A13 | | | D05540P | 3 | | | 150-151 |
| 013R | 22 | PH | | | 44-1 | 26-18-11 | D06204P | A13 | | | D05540P | 3 | | | 152-199 |
| 014R | 22 | PH | | | 44-1 | 26-18-21 | D06204P | A14 | \$D | | D05540P | 4 | | | ALL |
| 015R | 22 | PH | | | 44-1 | 26-18-31 | D06204P | A15 | \$D | | D05540P | 5 | | | ALL |
| 016 | 24 | PK | | | 1-0 | SPARE | D06204P | A16 | \$D | | D06204P | CAP | Y | | 050-099 |
| 017 | 24 | PK | | | 1-0 | SPARE | D06204P | A17 | \$D | | D06204P | CAP | Y | | ALL |
| 018R | 22 | PH | | | 44-1 | 26-18-12 | D06204P | A18 | \$D | | D05540P | 8 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1700
Page 8
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1704 | 286T1704 | | | EICAS-E8 TO P54,P37,P33 (continued) | | | | | | | | | | | | |
| 019 | 22 | | PA | 27-0 | 28-31-12 | D06204P | A19 | \$D | | D05372P | | 1 | | | 050-099, 155-199, 276-299 | |
| 019 | 24 | | PK | 1-0 | SPARE | D06204P | A19 | \$D | | D06204P | | CAP | Y | | 150-154, 275 | |
| 022 | 24 | | PK | 20-0 | 27-62-11 | D06204P | B02 | \$D | | D05332P | | 2 | | | ALL | |
| 023 | 24 | | PK | 20-0 | 30-31-21 | D06204P | B03 | \$D | | D05332P | | 3 | | | ALL | |
| 024 | 24 | | PK | 20-0 | 30-31-21 | D06204P | B04 | \$D | | D05332P | | 4 | | | ALL | |
| 025 | 24 | | PK | 20-0 | 30-31-23 | D06204P | B05 | \$D | | D05332P | | 5 | | | ALL | |
| 026 | 24 | | PK | 20-0 | 30-31-23 | D06204P | B06 | \$D | | D05332P | | 6 | | | ALL | |
| 027 | 24 | | PK | 20-0 | 30-32-21 | D06204P | B07 | \$D | | D05332P | | 7 | | | ALL | |
| 028 | 24 | | PK | 20-0 | SPARE | D06204P | B08 | \$D | | D05332P | | 8 | | | 150-199 | |
| 028 | 24 | | PK | 1-0 | SPARE | D06204P | B08 | \$D | | D06204P | | CAP | Y | | 275-299 | |
| 029 | 24 | | PK | 20-0 | 76-11-11 | D06204P | B09 | \$D | | D05332P | | 9 | | | ALL | |
| 030 | 24 | | PK | 20-0 | SPARE | D06204P | B10 | \$D | | D05332P | | 10 | | | ALL | |
| 031 | 24 | | PK | 20-0 | SPARE | D06204P | B11 | \$D | | D05332P | | 11 | | | ALL | |
| 032 | 24 | | PK | 20-0 | SPARE | D06204P | B12 | \$D | | D05332P | | 12 | | | ALL | |
| 033 | 24 | | PK | 20-0 | SPARE | D06204P | B13 | \$D | | D05332P | | 13 | | | ALL | |
| 034 | 24 | | PK | 20-0 | SPARE | D06204P | B14 | \$D | | D05332P | | 14 | | | ALL | |
| 035 | 24 | | PK | 20-0 | 29-11-22 | D06204P | B15 | \$D | | D05332P | | 15 | | | ALL | |
| 036 | 24 | | PK | 20-0 | 29-11-22 | D06204P | B16 | \$D | | D05332P | | 16 | | | ALL | |
| 037 | 22 | | PA | 27-0 | 28-42-13 | D06204P | B17 | \$D | | D05372P | | 20 | | | 050-099, 155-199, 276-299 | |
| 037 | 24 | | PK | 1-0 | SPARE | D06204P | B17 | \$D | | D06204P | | CAP | Y | | 150-154, 275 | |
| 038 | 24 | | PK | 27-0 | SPARE | D06204P | B18 | \$D | | D05372P | | 18 | | | ALL | |
| 039 | 24 | | PK | 27-0 | SPARE | D06204P | B19 | \$D | | D05372P | | 19 | | | ALL | |
| W1705 | 286T1705 | | | E8 RACK TO E1-4 SHELF | | | | | | | | | | | | |
| 002 | 24 | | PK | 19-0 | 34-21-31 | D05061P | A02 | \$D | | D04815J | | 2 | | | ALL | |
| 003 | 24 | | PK | 19-0 | 34-21-31 | D05061P | A03 | \$D | | D04815J | | 3 | | | ALL | |
| 004 | 24 | | PK | 19-0 | 34-21-31 | D05061P | A04 | \$D | | D04815J | | 4 | | | ALL | |
| 005 | 24 | | PK | 19-0 | SPARE | D05061P | A05 | \$D | | D04815J | | 5 | | | ALL | |
| 006 | 24 | | PK | 19-0 | SPARE | D05061P | A06 | \$D | | D04815J | | 6 | | | 150-199, 275-299 | |
| 007 | 24 | | PK | 19-0 | SPARE | D05061P | A07 | \$D | | D04815J | | 7 | | | ALL | |
| 008 | 24 | | PK | 19-0 | SPARE | D05061P | A08 | \$D | | D04815J | | 8 | | | ALL | |
| 009 | 24 | | PK | 19-0 | 22-14-31 | D05061P | A09 | \$D | | D04815J | | 9 | | | ALL | |
| 010 | 24 | | PK | 1-0 | SPARE | D05061P | A10 | \$D | | D05061P | | CAP | Y | | ALL | |
| 011 | 24 | | PK | 1-0 | SPARE | D05061P | A11 | \$D | | D05061P | | CAP | Y | | ALL | |
| 012 | 24 | | PK | 1-0 | SPARE | D05061P | A12 | \$D | | D05061P | | CAP | Y | | ALL | |
| 013 | 24 | | PK | 1-0 | SPARE | D05061P | A13 | \$D | | D05061P | | CAP | Y | | ALL | |
| 014 | 24 | | PK | 1-0 | SPARE | D05061P | A14 | \$D | | D05061P | | CAP | Y | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W1700

Page 9

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|-------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1705 | 286T1705 | | | E8 RACK TO E1-4 SHELF (continued) | | | | | | | | | | | |
| 015 | 24 | | PK | | 1-0 | SPARE | D05061P | A15 | \$D | | D05061P | | CAP | Y | ALL |
| 016 | 24 | | PK | | 1-0 | SPARE | D05061P | A16 | \$D | | D05061P | | CAP | Y | ALL |
| 017 | 24 | | PK | | 1-0 | SPARE | D05061P | A17 | \$D | | D05061P | | CAP | Y | ALL |
| 018 | 24 | | PK | | 1-0 | SPARE | D05061P | A18 | \$D | | D05061P | | CAP | Y | ALL |
| 019 | 24 | | PK | | 1-0 | SPARE | D05061P | A19 | \$D | | D05061P | | CAP | Y | ALL |
| W1706 | 286T1706 | | | EICAS-E8 TO P61 | | | | | | | | | | | |
| 002 | 24 | | PK | | 30-0 | 29-21-32 | D06206P | A02 | \$D | | D05402P | | 2 | | ALL |
| 003 | 24 | | PK | | 30-0 | 21-31-21 | D06206P | A03 | \$D | | D05402P | | 3 | | ALL |
| 004 | 24 | | PK | | 30-0 | 24-51-13 | D06206P | A04 | \$D | | D05402P | | 4 | | ALL |
| 005 | 24 | | PK | | 30-0 | 27-13-11 | D06206P | A05 | \$D | | D05402P | | 5 | | ALL |
| 006 | 24 | | PK | | 30-0 | 29-11-22 | D06206P | A06 | \$D | | D05402P | | 6 | | ALL |
| 007 | 24 | | PK | | 30-0 | 29-11-31 | D06206P | A07 | \$D | | D05402P | | 7 | | ALL |
| 008 | 24 | | PK | | 30-0 | SPARE | D06206P | A08 | \$D | | D05402P | | 8 | | ALL |
| 009 | 24 | | PK | | 2-0 | SPARE | D06206P | A09 | \$D | | D06206P | | CAP | Y | 150-199 |
| 009 | 24 | | PK | | 1-0 | SPARE | D06206P | A09 | \$D | | D06206P | | CAP | Y | 275-299 |
| 010 | 24 | | PK | | 1-0 | SPARE | D06206P | A10 | \$D | | D06206P | | CAP | Y | 150-199, 275-299 |
| 011 | 24 | | PK | | 30-0 | 36-11-31 | D06206P | A11 | \$D | | D05402P | | 11 | | ALL |
| 012 | 24 | | PK | | 30-0 | 29-32-11 | D06206P | A12 | \$D | | D05402P | | 12 | | ALL |
| 013 | 24 | | PK | | 30-0 | 29-32-11 | D06206P | A13 | \$D | | D05402P | | 13 | | ALL |
| 014 | 24 | | PK | | 30-0 | 30-21-11 | D06206P | A14 | \$D | | D05402P | | 14 | | ALL |
| 015 | 24 | | PK | | 30-0 | SPARE | D06206P | A15 | \$D | | D05402P | | 15 | | 050-099, 150-199 |
| 015 | 24 | | PK | | 30-0 | 30-21-11 | D06206P | A15 | \$D | | D05402P | | 15 | | 275-299 |
| 016 | 24 | | PK | | 1-0 | SPARE | D06206P | A16 | \$D | | D06206P | | CAP | Y | 150-199, 275-299 |
| 017 | 24 | | PK | | 1-0 | SPARE | D06206P | A17 | \$D | | D06206P | | CAP | Y | 150-199, 275-299 |
| 018 | 24 | | PK | | 1-0 | SPARE | D06206P | A18 | \$D | | D06206P | | CAP | Y | 150-199, 275-299 |
| 019 | 22 | | PA | | 30-0 | 28-31-11 | D06206P | A19 | \$D | | D05402P | | 1 | | 050-099, 155-199, 276-299 |
| 019 | 24 | | PK | | 1-0 | SPARE | D06206P | A19 | \$D | | D06206P | | CAP | Y | 150-154, 275 |
| W1709 | 286T1709 | | | TCAS COAX-FROM E1-3 SHELF TO E2-3(B297) | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D02463C | = C12 | | | D02539 | | = C1 | | 050-099, 150-199, 277-299 |
| 01CX | | | | BR A | 5-6 | 34-45-11 | D02463C | | 12 | | D02539 | | = A1 | | 050-099, 150-154, 277-299 |
| 01CX | | | | BR A | 5-8 | 34-45-11 | D02463C | | 12 | | D02539 | | = A1 | | 155-199 |

WIRE LIST
D280T132

91-21-11
Section W1700
Page 10 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----------------------------|-------------|----------|---------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1710 | 286T1710 | | | EICAS-E8 TO P61 (LB) | | | | | | | | | | | | |
| 002 | 24 | | PK | 27-0 | 33-51-11 | D06210P | A02 | \$D | | D05406P | 2 | | | ALL | | |
| 003 | 24 | | PK | 27-0 | 21-61-51 | D06210P | A03 | \$D | | D05406P | 3 | | | ALL | | |
| 004 | 24 | | PK | 27-0 | 24-51-23 | D06210P | A04 | \$D | | D05406P | 4 | | | ALL | | |
| 005 | 24 | | PK | 27-0 | 27-13-11 | D06210P | A05 | \$D | | D05406P | 5 | | | ALL | | |
| 006 | 24 | | PK | 27-0 | 29-11-12 | D06210P | A06 | \$D | | D05406P | 6 | | | ALL | | |
| 007 | 24 | | PK | 27-0 | 28-42-12 | D06210P | A07 | \$D | | D05406P | 7 | | | ALL | | |
| 008R | 22 | | PH | 27-0 | SPARE | D06210P | A08 | \$D | | D05406P | 8 | | | 150-199 | | |
| 008R | 22 | | PH | 1-0 | SPARE | D06210P | A08 | \$D | | D06210P | CAP | Y | | 275-299 | | |
| 009R | 22 | | PH | 27-0 | SPARE | D06210P | A09 | \$D | | D05406P | 9 | | | 150-199 | | |
| 009R | 22 | | PH | 1-0 | SPARE | D06210P | A09 | \$D | | D06210P | CAP | Y | | 275-299 | | |
| 010R | 22 | | PH | 27-0 | SPARE | D06210P | A10 | \$D | | D05406P | 10 | | | 150-199 | | |
| 010R | 22 | | PH | 1-0 | SPARE | D06210P | A10 | \$D | | D06210P | CAP | Y | | 275-299 | | |
| 011 | 24 | | PK | 27-0 | 36-11-21 | D06210P | A11 | \$D | | D05406P | 11 | | | ALL | | |
| 012 | 24 | | PK | 27-0 | 21-26-21 | D06210P | A12 | \$D | | D05406P | 12 | | | ALL | | |
| 019 | 24 | | PK | 1-0 | SPARE | D06210P | A19 | \$D | | D06210P | CAP | Y | | 050-099, 275-299 | | |
| 019 | 24 | | PK | 2-0 | SPARE | D06210P | A19 | \$D | | D06210P | CAP | Y | | 150-199 | | |
| 022 | 24 | | PK | 27-0 | 24-51-43 | D06210P | B02 | \$D | | D05406P | 22 | | | ALL | | |
| 023 | 24 | | PK | 27-0 | 29-32-11 | D06210P | B03 | \$D | | D05406P | 23 | | | ALL | | |
| 024 | 24 | | PK | 27-0 | 29-32-11 | D06210P | B04 | \$D | | D05406P | 24 | | | ALL | | |
| 025 | 24 | | PK | 27-0 | 30-41-12 | D06210P | B05 | \$D | | D05406P | 25 | | | ALL | | |
| 026 | 24 | | PK | 27-0 | 30-41-12 | D06210P | B06 | \$D | | D05406P | 26 | | | ALL | | |
| 027 | 24 | | PK | 27-0 | 29-11-31 | D06210P | B07 | \$D | | D05406P | 27 | | | ALL | | |
| 028 | 24 | | PK | 27-0 | SPARE | D06210P | B08 | \$D | | D05406P | 28 | | | 150-199, 275-299 | | |
| 029 | 24 | | PK | 27-0 | 32-42-12 | D06210P | B09 | \$D | | D05406P | 29 | | | ALL | | |
| 030R | 22 | | PH | 27-0 | SPARE | D06210P | B10 | \$D | | D05406P | 30 | | | 150-199 | | |
| 030R | 22 | | PH | 1-0 | SPARE | D06210P | B10 | \$D | | D06210P | CAP | Y | | 275-299 | | |
| 031R | 22 | | PH | 27-0 | SPARE | D06210P | B11 | \$D | | D05406P | 31 | | | 150-199 | | |
| 031R | 22 | | PH | 1-0 | SPARE | D06210P | B11 | \$D | | D06210P | CAP | Y | | 275-299 | | |
| 032 | 24 | | PK | 27-0 | SPARE | D06210P | B12 | \$D | | D05406P | 32 | | | 150-199, 275-299 | | |
| 033 | 24 | | PK | 27-0 | SPARE | D06210P | B13 | \$D | | D05406P | 33 | | | ALL | | |
| 034 | 24 | | PK | 27-0 | 30-21-11 | D06210P | B14 | \$D | | D05406P | 34 | | | ALL | | |
| 035 | 24 | | PK | 27-0 | SPARE | D06210P | B15 | \$D | | D05406P | 35 | | | 050-099, 150-199 | | |
| 035 | 24 | | PK | 27-0 | 30-21-11 | D06210P | B15 | \$D | | D05406P | 35 | | | 275-299 | | |
| 036 | 24 | | PK | 27-0 | 21-58-16 | D06210P | B16 | \$D | | D05406P | 36 | | | ALL | | |
| 039 | 24 | | PK | 1-0 | SPARE | D06210P | B19 | \$D | | D06210P | CAP | Y | | 150-199, 275-299 | | |
| 201B | 24 | | PL | IA | 27-0 | 21-65-11 | D06210P | A13 | \$D | D05406P | 13 | | | ALL | | |
| 201R | 24 | | PL | IA | 0-0 | 21-65-11 | D06210P | A14 | \$D | D05406P | 14 | | | ALL | | |
| 202B | 24 | | PL | IB | 27-0 | 21-65-11 | D06210P | A15 | \$D | D05406P | 15 | | | ALL | | |
| 202R | 24 | | PL | IB | 0-0 | 21-65-11 | D06210P | A16 | \$D | D05406P | 16 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W1710

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1710 | 286T1710 | | | EICAS-E8 TO P61 (LB) (continued) | | | | | | | | | | | | |
| 203B | 24 | PL | IC | 27-0 | 21-65-11 | D06210P | A17 | \$D | | D05406P | 17 | | | ALL | | |
| 203R | 24 | PL | IC | 0-0 | 21-65-11 | D06210P | A18 | \$D | | D05406P | 18 | | | ALL | | |
| 204B | 24 | PL | ID | 27-0 | 21-65-11 | D06210P | B17 | \$D | | D05406P | 37 | | | ALL | | |
| 204R | 24 | PL | ID | 0-0 | 21-65-11 | D06210P | B18 | \$D | | D05406P | 38 | | | ALL | | |
| W1711 | 286T1711 | | | EICAS DISPLAY SELECT PNL(P9) TO P61 AND P1 PNL | | | | | | | | | | | | |
| 001 | 22 | PA | | 23-0 | 31-41-11 | D00209 | | | 38 | D05117J | 1 | | | ALL | | |
| 002 | 20 | PA | | 4-0 | 31-41-11 | D00209 | | | 39 | GD00207 | A.. | 2 | | ALL | | |
| 003 | 20 | PA | | 4-0 | 31-41-11 | D00209 | | | 37 | GD00207 | S.. | 2 | | ALL | | |
| 005 | 20 | PA | | 4-0 | 31-41-12 | D00209 | | | 36 | GD00207 | D.. | 2 | | ALL | | |
| 006 | 22 | PA | | 23-0 | 31-41-12 | D00209 | | | 1 | D05115J | 4 | | | ALL | | |
| 007 | 22 | PA | | 23-0 | 31-41-12 | D00209 | | | 2 | D05115J | 5 | | | ALL | | |
| 011 | 24 | PK | | 33-0 | 31-41-13 | D00209 | | | 27 | D05311P | 5 | | | ALL | | |
| 012 | 24 | PK | | 33-0 | 31-41-13 | D00209 | | | 31 | D05311P | 6 | | | ALL | | |
| 013 | 24 | PK | | 33-0 | 31-41-13 | D00209 | | | 32 | D05311P | 7 | | | ALL | | |
| 014 | 24 | PK | | 33-0 | 31-41-13 | D00209 | | | 28 | D05311P | 8 | | | ALL | | |
| 015 | 24 | PK | | 33-0 | 31-41-13 | D00209 | | | 4 | D05311P | 9 | | | ALL | | |
| 018 | 24 | PK | | 33-0 | 31-41-13 | D00209 | | | 26 | D05311P | 12 | | | ALL | | |
| 019 | 24 | PK | | 33-0 | 31-41-13 | D00209 | | | 29 | D05311P | 13 | | | ALL | | |
| 020 | 24 | PK | | 33-0 | 31-41-13 | D00209 | | | 34 | D05311P | 14 | | | ALL | | |
| 021 | 24 | PK | | 33-0 | 31-41-13 | D00209 | | | 35 | D05311P | 15 | | | ALL | | |
| 022 | 24 | PK | | 33-0 | 31-41-13 | D00209 | | | 3 | D05311P | 16 | | | ALL | | |
| 025 | 22 | PA | | 23-0 | 31-41-17 | D00209 | | | 9 | D05115J | 17 | | | ALL | | |
| 026 | 22 | PA | | 23-0 | 31-41-17 | D00209 | | | 8 | D05115J | 18 | | | ALL | | |
| 027 | 24 | PK | | 29-0 | SPARE | D05311P | | | 19 | D05115J | 19 | | | ALL | | |
| 028 | 24 | PK | | 29-0 | SPARE | D05311P | | | 20 | D05115J | 20 | | | ALL | | |
| 029 | 24 | PK | | 29-0 | SPARE | D05311P | | | 21 | D05117J | 19 | | | ALL | | |
| 030 | 24 | PK | | 29-0 | SPARE | D05311P | | | 22 | D05117J | 20 | | | ALL | | |
| 034 | 18 | PA | | 16-0 | 33-13-18 | D00209 | | DK | 40 | SP02292 | | | 9 | ALL | | |
| 035 | 18 | PA | | 4-0 | 33-13-18 | D00209 | | DK | 41 | GD00207 | A.. | 2 | | ALL | | |
| 036 | 24 | PK | | 33-0 | 31-41-13 | D00209 | | | 33 | D05311P | 31 | | | ALL | | |
| 201B | 24 | PW | IA | 23-0 | 31-41-12 | D00209 | | | 20 | D05117J | 3 | | | ALL | | |
| 201R | 24 | PW | IA | 0-0 | 31-41-12 | D00209 | | | 19 | D05117J | 2 | | | ALL | | |
| 201Z | | | IA | 0-0 | 31-41-12 | GD00207 | | | S.. | 2 | D05117J | 4 | | ALL | | |
| 202B | 24 | PW | IB | 23-0 | 31-41-12 | D00209 | | | 18 | D05115J | 2 | | | ALL | | |
| 202R | 24 | PW | IB | 0-0 | 31-41-12 | D00209 | | | 17 | D05115J | 1 | | | ALL | | |
| 202Z | | | IB | 0-0 | 31-41-12 | GD00207 | | | S.. | 2 | D05115J | 3 | | ALL | | |
| 206B | 24 | PL | IF | 3-0 | SPARE | D05117J | | | 17 | D05115J | 27 | | | ALL | | |
| 206R | 24 | PL | IF | 0-0 | SPARE | D05117J | | | 16 | D05115J | 26 | | | ALL | | |

WIRE LIST

D280T132

91-21-11
Section W1710
Page 2
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|-------|------|------|---------|-----|-------------|--|--|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | | |
| W1711 | 286T1711 | | | EICAS DISPLAY SELECT PNL(P9) TO P61 AND P1 PNL (continued) | | | | | | | | | | | | | | | |
| 301B | 24 | | PM | MA | 23-0 | 31-41-14 | D05117J | | | | 6 | | | D00209 | | 15 | | | ALL |
| 301R | 24 | | PM | MA | 0-0 | 31-41-14 | D05117J | | | | 5 | | | D00209 | | 14 | | | ALL |
| 301Y | 24 | | PM | MA | 0-0 | 31-41-14 | D05117J | | | | 7 | | | D00209 | | 16 | | | ALL |
| 302B | 24 | | PM | MB | 23-0 | 31-41-14 | D05115J | | | | 13 | | | D00209 | | 12 | | | ALL |
| 302R | 24 | | PM | MB | 0-0 | 31-41-14 | D05115J | | | | 12 | | | D00209 | | 11 | | | ALL |
| 302Y | 24 | | PM | MB | 0-0 | 31-41-14 | D05115J | | | | 14 | | | D00209 | | 13 | | | ALL |
| W1712 | 286T1712 | | | EICAS-E8 TO P37,E2 | | | | | | | | | | | | | | | |
| 002 | 24 | | PK | | 25-0 | 21-25-21 | D06212P | A02 | \$D | | | | | D05374P | | 2 | | | ALL |
| 003 | 24 | | PK | | 25-0 | 27-81-11 | D06212P | A03 | \$D | | | | | D05374P | | 3 | | | ALL |
| 004 | 24 | | PK | | 25-0 | 21-61-11 | D06212P | A04 | \$D | | | | | D05374P | | 4 | | | ALL |
| 005 | 24 | | PK | | 25-0 | 21-61-21 | D06212P | A05 | \$D | | | | | D05374P | | 5 | | | ALL |
| 006 | 24 | | PK | | 25-0 | 21-61-31 | D06212P | A06 | \$D | | | | | D05374P | | 6 | | | ALL |
| 007 | 24 | | PK | | 25-0 | 30-21-11 | D06212P | A07 | \$D | | | | | D05374P | | 7 | | | 050-099, 150-199 |
| 007 | 24 | | PK | | 25-0 | SPARE | D06212P | A07 | \$D | | | | | D05374P | | 7 | | | 275-299 |
| 008 | 24 | | PK | | 25-0 | SPARE | D06212P | A08 | \$D | | | | | D05374P | | 8 | | | ALL |
| 009 | 24 | | PK | | 25-0 | 21-61-41 | D06212P | A09 | \$D | | | | | D05374P | | 9 | | | ALL |
| 010 | 24 | | PK | | 25-0 | 29-33-11 | D06212P | A10 | \$D | | | | | D05374P | | 10 | | | ALL |
| 011 | 24 | | PK | | 25-0 | 28-42-11 | D06212P | A11 | \$D | | | | | D05374P | | 11 | | | ALL |
| 014 | 24 | | PK | | 25-0 | 27-23-11 | D06212P | A14 | \$D | | | | | D05374P | | 14 | | | ALL |
| 015 | 24 | | PK | | 25-0 | 29-11-12 | D06212P | A15 | \$D | | | | | D05374P | | 15 | | | ALL |
| 016 | 24 | | PK | | 25-0 | 29-11-12 | D06212P | A16 | \$D | | | | | D05374P | | 16 | | | ALL |
| 017 | 24 | | PK | | 25-0 | 29-32-11 | D06212P | A17 | \$D | | | | | D05374P | | 17 | | | ALL |
| 018 | 24 | | PK | | 25-0 | 29-32-11 | D06212P | A18 | \$D | | | | | D05374P | | 18 | | | ALL |
| 019 | 24 | | PK | | 25-0 | 79-35-11 | D06212P | A19 | \$D | | | | | D05374P | | 19 | | | ALL |
| 022 | 24 | | PK | | 25-0 | SPARE | D06212P | B02 | \$D | | | | | D05374P | | 22 | | | ALL |
| 023 | 24 | | PK | | 25-0 | SPARE | D06212P | B03 | \$D | | | | | D05374P | | 23 | | | ALL |
| 024 | 24 | | PK | | 1-0 | SPARE | D06212P | B04 | \$D | | | | | D06212P | CAP | Y | | | 050-099, 150-199 |
| 024 | 24 | | PK | | 25-0 | SPARE | D06212P | B04 | \$D | | | | | D05374P | | 24 | | | 275-299 |
| 025 | 24 | | PK | | 25-0 | 75-23-11 | D06212P | B05 | \$D | | | | | D05374P | | 25 | | | ALL |
| 028 | 24 | | PK | | 25-0 | SPARE | D06212P | B08 | \$D | | | | | D05374P | | 28 | | | 150-154, 275 |
| 029 | 24 | | PK | | 25-0 | SPARE | D06212P | B09 | \$D | | | | | D05374P | | 29 | | | ALL |
| 033 | 24 | | PK | | 25-0 | 32-09-12 | D06212P | B13 | \$D | | | | | D05374P | | 33 | | | ALL |
| 034 | 24 | | PK | | 25-0 | 32-09-12 | D06212P | B14 | \$D | | | | | D05374P | | 34 | | | ALL |
| 035 | 24 | | PK | | 25-0 | 24-11-21 | D06212P | B15 | \$D | | | | | D05374P | | 35 | | | 050-099, 275-299 |
| 035 | 24 | | PK | | 24-0 | 24-11-21 | D06212P | B15 | \$D | | | | | D05374P | | 35 | | | 150-199 |
| 036 | 24 | | PK | | 25-0 | 30-21-11 | D06212P | B16 | \$D | | | | | D05374P | | 36 | | | ALL |
| 037 | 24 | | PK | | 1-0 | SPARE | D06212P | B17 | \$D | | | | | D06212P | CAP | Y | | | 275-299 |
| 038 | 24 | | PK | | 25-0 | 21-44-11 | D06212P | B18 | \$D | | | | | D05374P | | 38 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1710

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1712 | 286T1712 | | | EICAS-E8 TO P37,E2 (continued) | | | | | | | | | | | |
| 039 | 24 | | PK | | 25-0 | 29-33-11 | D06212P | B19 | \$D | | D05374P | 39 | | | ALL |
| 042 | 24 | | PK | | 26-0 | 29-32-11 | D06214P | A02 | \$D | | D05374P | 42 | | | ALL |
| 043 | 24 | | PK | | 1-0 | SPARE | D06214P | A03 | \$D | | D06214P | CAP | Y | | ALL |
| 044 | 24 | | PK | | 1-0 | SPARE | D06214P | A04 | \$D | | D06214P | CAP | Y | | ALL |
| 045 | 24 | | PK | | 26-0 | 30-21-11 | D06214P | A12 | \$D | | D05374P | 45 | | | 050-099, 150-199 |
| 045 | 24 | | PK | | 26-0 | 30-21-11 | D06214P | A05 | \$D | | D05374P | 45 | | | 275-299 |
| 046 | 24 | | PK | | 26-0 | 28-22-21 | D06214P | A06 | \$D | | D05374P | 46 | | | ALL |
| 047 | 24 | | PK | | 26-0 | 73-33-11 | D06214P | A07 | \$D | | D05374P | 47 | | | ALL |
| 048 | 24 | | PK | | 26-0 | 73-33-11 | D06214P | A08 | \$D | | D05374P | 48 | | | ALL |
| 051 | 24 | | PK | | 26-0 | 79-33-11 | D06214P | A11 | \$D | | D05374P | 51 | | | ALL |
| 052 | 24 | | PK | | 1-0 | SPARE | D06214P | A12 | \$D | | D06214P | CAP | Y | | 275-299 |
| 053 | 24 | | PK | | 26-0 | 73-33-11 | D06214P | A13 | \$D | | D05374P | CAP | Y | | 050-099 |
| 053 | 24 | | PK | | 1-0 | SPARE | D06214P | A13 | \$D | | D06214P | CAP | Y | | 150-154, 275-299 |
| 054 | 24 | | PK | | 26-0 | 73-21-18 | D06214P | A14 | \$D | | D05374P | 54 | | | ALL |
| 055 | 22 | | PA | | 24-0 | 28-31-11 | D06214P | A15 | \$D | | D05374P | 1 | | | 050-099, 155-199, 276-299 |
| 055 | 24 | | PK | | 1-0 | SPARE | D06214P | A15 | \$D | | D06214P | CAP | Y | | 150-154, 275 |
| 056 | 24 | | PK | | 24-0 | 28-42-13 | D06214P | A16 | \$D | | D05374P | 28 | | | 050-099 |
| 056 | 24 | | PK | | 1-0 | SPARE | D06214P | A16 | \$D | | D06214P | CAP | Y | | 150-154, 275 |
| 056 | 22 | | PA | | 24-0 | 28-42-13 | D06214P | A16 | \$D | | D05374P | 28 | | | 155-199, 276-299 |
| 202B | 24 | | PW | AB | 26-0 | 77-12-11 | D06212P | B07 | \$D | | D05374P | 41 | | | 050-099 |
| 202B | 24 | | PW | AB | 25-0 | 77-12-11 | D06212P | B07 | \$D | | D05374P | 41 | | | 150-199, 275-299 |
| 202R | 24 | | PW | AB | 0-0 | 77-12-11 | D06212P | B06 | \$D | | D05374P | 44 | | | 050-099, 162-199, 277-299 |
| 202R | 24 | | PW | AB | 0-0 | 77-12-11 | D06212P | B06 | \$D | | D05374P | 40 | | | 150-157, 275-276 |
| 202Z | | | | AB | 0-0 | 77-12-11 | D06212P | B01 | \$D | | D05374P | 52 | | | ALL |
| 204B | 24 | | PL | ID | 26-0 | 36-22-21 | D06214P | A09 | \$D | | D05374P | 49 | | | ALL |
| 204R | 24 | | PL | ID | 0-0 | 36-22-21 | D06214P | A10 | \$D | | D05374P | 50 | | | ALL |
| 205B | 24 | | PL | AC | 25-0 | 29-31-11 | D05374P | 13 | | | D06212P | A13 | \$D | | ALL |
| 205R | 24 | | PL | AC | 0-0 | 29-31-11 | D05374P | 12 | | | D06212P | A12 | \$D | | ALL |
| 207B | 24 | | PW | IG | 26-0 | 73-21-14 | D05374P | 26 | | | D06214P | A18 | \$D | | 050-099, 150-199 |
| 207B | 24 | | PW | AD | 24-0 | 73-21-14 | D06214P | A18 | \$D | | D05374P | 26 | | | 275-299 |
| 207R | 24 | | PW | IG | 0-0 | 73-21-14 | D05374P | 27 | | | D06214P | A19 | \$D | | 050-099, 150-199 |
| 207R | 24 | | PW | AD | 0-0 | 73-21-14 | D06214P | A19 | \$D | | D05374P | 27 | | | 275-299 |
| 207Z | | | | IG | 0-0 | 73-21-14 | D05374P | 20 | | | D06214P | A17 | \$D | | 050-099, 150-199 |
| 207Z | | | | AD | 0-0 | 73-21-14 | D06214P | A17 | \$D | | D05374P | 20 | | | 275-299 |
| 301B | 24 | | PM | MA | 25-0 | 79-31-11 | D06212P | B11 | \$D | | D05374P | 31 | | | ALL |
| 301R | 24 | | PM | MA | 0-0 | 79-31-11 | D06212P | B10 | \$D | | D05374P | 30 | | | ALL |
| 301Y | 24 | | PM | MA | 0-0 | 79-31-11 | D06212P | B12 | \$D | | D05374P | 32 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W1710
Page 4
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--------------------------------|-------------|----------|---------|------|------|---------|-------|------|------|--------|-------------|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1716 | 286T1716 | | | EICAS-E8 TO P4 | | | | | | | | | | | | |
| 002 | 24 | | PK | 27-3 | SPARE | D06216P | A02 | \$D | | D05410P | | | | 2 | | ALL |
| 003 | 24 | | PK | 27-3 | 35-21-11 | D06216P | A03 | \$D | | D05410P | | | | 3 | | ALL |
| 004 | 24 | | PK | 27-3 | 28-22-31 | D06216P | A04 | \$D | | D05410P | | | | 4 | | ALL |
| 005 | 24 | | PK | 27-3 | 80-11-21 | D06216P | A05 | \$D | | D05410P | | | | 5 | | ALL |
| 006 | 24 | | PK | 27-3 | 80-11-21 | D06216P | A06 | \$D | | D05410P | | | | 6 | | ALL |
| 007 | 24 | | PK | 27-3 | 29-32-11 | D06216P | A07 | \$D | | D05410P | | | | 7 | | ALL |
| 008 | 24 | | PK | 27-3 | 32-42-11 | D06216P | A08 | \$D | | D05410P | | | | 8 | | ALL |
| 009 | 24 | | PK | 27-3 | 24-28-11 | D06216P | A09 | \$D | | D05410P | | | | 9 | | ALL |
| 010 | 24 | | PK | 27-3 | 24-33-11 | D06216P | A10 | \$D | | D05410P | | | | 10 | | ALL |
| 011 | 24 | | PK | 27-3 | 24-33-11 | D06216P | A11 | \$D | | D05410P | | | | 11 | | ALL |
| 012 | 24 | | PK | 27-3 | SPARE | D06216P | A12 | \$D | | D05410P | | | | 12 | | ALL |
| 013 | 24 | | PK | 27-3 | SPARE | D06216P | A13 | \$D | | D05410P | | | | 13 | | ALL |
| 014 | 24 | | PK | 1-0 | SPARE | D06216P | A14 | \$D | | D06216P | | CAP | Y | | | 150-199, 275-299 |
| 015 | 24 | | PK | 1-0 | SPARE | D06216P | A15 | \$D | | D06216P | | CAP | Y | | | 150-199, 275-299 |
| 016 | 24 | | PK | 27-3 | 74-31-11 | D06216P | A16 | \$D | | D05410P | | | | 16 | | ALL |
| 017 | 24 | | PK | 27-3 | SPARE | D06216P | A17 | \$D | | D05410P | | | | 17 | | ALL |
| 018 | 24 | | PK | 27-3 | 29-11-32 | D06216P | A18 | \$D | | D05410P | | | | 18 | | ALL |
| 019 | 24 | | PK | 27-3 | SPARE | D06216P | A19 | \$D | | D05410P | | | | 19 | | ALL |
| 028 | 24 | | PK | 27-3 | 24-34-11 | D06216P | B08 | \$D | | D05410P | | | | 28 | | ALL |
| 029 | 24 | | PK | 27-3 | 24-34-11 | D06216P | B09 | \$D | | D05410P | | | | 29 | | ALL |
| 030 | 24 | | PK | 27-3 | 24-34-11 | D06216P | B10 | \$D | | D05410P | | | | 30 | | ALL |
| 031 | 24 | | PK | 27-3 | 24-34-11 | D06216P | B11 | \$D | | D05410P | | | | 31 | | ALL |
| 032 | 24 | | PK | 27-3 | 21-58-16 | D06216P | B12 | \$D | | D05410P | | | | 32 | | ALL |
| 033 | 24 | | PK | 27-3 | 24-34-11 | D06216P | B13 | \$D | | D05410P | | | | 33 | | ALL |
| 034 | 24 | | PK | 27-3 | 24-34-11 | D06216P | B14 | \$D | | D05410P | | | | 34 | | ALL |
| 201B | 24 | | PL | IA | 27-3 | 24-34-11 | D06216P | B03 | \$D | D05410P | | | | 23 | | ALL |
| 201R | 24 | | PL | IA | 0-0 | 24-34-11 | D06216P | B02 | \$D | D05410P | | | | 22 | | ALL |
| 202B | 24 | | PL | IB | 27-3 | 24-34-11 | D06216P | B05 | \$D | D05410P | | | | 25 | | ALL |
| 202R | 24 | | PL | IB | 0-0 | 24-34-11 | D06216P | B04 | \$D | D05410P | | | | 24 | | ALL |
| 203B | 24 | | PL | IC | 27-3 | 24-34-11 | D06216P | B07 | \$D | D05410P | | | | 27 | | ALL |
| 203R | 24 | | PL | IC | 0-0 | 24-34-11 | D06216P | B06 | \$D | D05410P | | | | 26 | | ALL |
| 204B | 24 | | PL | ID | 27-3 | 35-11-13 | D06216P | B15 | \$D | D05410P | | | | 35 | | ALL |
| 204R | 24 | | PL | ID | 0-0 | 35-11-13 | D06216P | B16 | \$D | D05410P | | | | 36 | | ALL |
| 301B | 24 | | PM | IE | 27-3 | 49-94-14 | D06216P | B17 | \$D | D05410P | | | | 37 | | ALL |
| 301R | 24 | | PM | IE | 0-0 | 49-94-14 | D06216P | B18 | \$D | D05410P | | | | 38 | | ALL |
| 301Y | 24 | | PM | IE | 0-0 | 49-94-14 | D06216P | B19 | \$D | D05410P | | | | 39 | | ALL |
| W1718 | 286T1718 | | | EICAS-E8 TO P36,P37,P54 | | | | | | | | | | | | |
| 002R | 22 | | PH | 43-0 | 26-11-11 | D06218P | A02 | \$D | | D05546P | | | | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W1710

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1718 | 286T1718 | | | EICAS-E8 TO P36,P37,P54 (continued) | | | | | | | | | | | | |
| 003R | 22 | | PH | 43-0 | 26-11-12 | D06218P | A03 | \$D | | D05546P | 3 | | | ALL | | |
| 004R | 22 | | PH | 43-0 | 26-11-21 | D06218P | A04 | \$D | | D05546P | 4 | | | ALL | | |
| 005R | 22 | | PH | 43-0 | 26-11-22 | D06218P | A05 | \$D | | D05546P | 5 | | | ALL | | |
| 006R | 22 | | PH | 43-0 | 26-15-11 | D06218P | A06 | \$D | | D05546P | 6 | | | ALL | | |
| 007R | 22 | | PH | 43-0 | 26-11-11 | D06218P | A07 | \$D | | D05546P | 7 | | | ALL | | |
| 008R | 22 | | PH | 43-0 | 26-11-12 | D06218P | A08 | \$D | | D05546P | 8 | | | ALL | | |
| 009 | 24 | | PK | 43-0 | SPARE | D06218P | A09 | \$D | | D05546P | 9 | | | ALL | | |
| 010R | 22 | | PH | 43-0 | 26-11-11 | D06218P | A10 | \$D | | D05546P | 10 | | | ALL | | |
| 014 | 24 | | PK | 10-0 | 28-22-31 | D06218P | A14 | \$D | | D05366P | 4 | | | ALL | | |
| 015 | 24 | | PK | 10-0 | 27-23-11 | D06218P | A15 | \$D | | D05366P | 5 | | | ALL | | |
| 016 | 24 | | PK | 10-0 | 28-42-21 | D06218P | A16 | \$D | | D05366P | 6 | | | ALL | | |
| 017 | 24 | | PK | 10-0 | 31-31-13 | D06218P | A17 | \$D | | D05366P | 7 | | | ALL | | |
| 018 | 24 | | PK | 10-0 | 29-11-32 | D06218P | A18 | \$D | | D05366P | 8 | | | ALL | | |
| 019 | 24 | | PK | 10-0 | 32-41-11 | D06218P | A19 | \$D | | D05366P | 9 | | | ALL | | |
| 022R | 22 | | PH | 25-0 | 26-21-11 | D06218P | B02 | \$D | | D05376P | 2 | | | ALL | | |
| 023R | 22 | | PH | 25-0 | 26-23-12 | D06218P | B03 | \$D | | D05376P | 3 | | | ALL | | |
| 024 | 24 | | PK | 25-0 | 29-21-31 | D06218P | B04 | \$D | | D05376P | 4 | | | ALL | | |
| 026 | 24 | | PK | 25-0 | 76-11-11 | D06218P | B06 | \$D | | D05376P | 6 | | | ALL | | |
| 027 | 24 | | PK | 25-0 | 76-11-11 | D06218P | B07 | \$D | | D05376P | 7 | | | ALL | | |
| 028 | 24 | | PK | 25-0 | 26-16-21 | D06218P | B08 | \$D | | D05376P | 8 | | | ALL | | |
| 029 | 24 | | PK | 25-0 | 26-16-21 | D06218P | B09 | \$D | | D05376P | 9 | | | ALL | | |
| 030 | 24 | | PK | 10-0 | 32-42-11 | D06218P | B10 | \$D | | D05366P | 10 | | | ALL | | |
| 031 | 24 | | PK | 10-0 | 32-42-11 | D06218P | B11 | \$D | | D05366P | 11 | | | ALL | | |
| 032 | 24 | | PK | 10-0 | 32-44-11 | D06218P | B12 | \$D | | D05366P | 12 | | | ALL | | |
| 033 | 24 | | PK | 10-0 | 32-42-11 | D06218P | B13 | \$D | | D05366P | 13 | | | ALL | | |
| 036R | 24 | | PP | 43-0 | 26-16-11 | D06218P | B16 | \$D | | D05546P | 12 | | | ALL | | |
| 037R | 24 | | PP | 43-0 | 26-16-11 | D06218P | B17 | \$D | | D05546P | 13 | | | ALL | | |
| 038R | 24 | | PP | 43-0 | 26-16-11 | D06218P | B18 | \$D | | D05546P | 14 | | | ALL | | |
| 039 | 24 | | PK | 43-0 | SPARE | D06218P | B19 | \$D | | D05546P | 15 | | | ALL | | |
| 202B | 24 | | PW | IB | 10-0 | 73-21-14 | D06218P | B15 | \$D | D05366P | 14 | | | ALL | | |
| 202R | 24 | | PW | IB | 0-0 | 73-21-14 | D06218P | B14 | \$D | D05366P | 15 | | | ALL | | |
| 202Z | | | | IB | 0-0 | 73-21-14 | D06218P | B05 | \$D | D05366P | 16 | | | ALL | | |
| 207B | 24 | | PW | IA | 10-0 | 77-12-11 | D06218P | A12 | \$D | D05366P | 20 | | | 050-099, 275-299 | | |
| 207B | 24 | | PW | IA | 10-0 | 77-12-11 | D06218P | A12 | | D05366P | 20 | | | 150-199 | | |
| 207R | 24 | | PW | IA | 0-0 | 77-12-11 | D06218P | A11 | \$D | D05366P | 19 | | | 050-099, 275-299 | | |
| 207R | 24 | | PW | IA | 0-0 | 77-12-11 | D06218P | A11 | | D05366P | 19 | | | 150-199 | | |
| 207Z | | | | IA | 0-0 | 77-12-11 | D06218P | A13 | \$D | D05366P | 18 | | | 050-099, 275-299 | | |
| 207Z | | | | IA | 0-0 | 77-12-11 | D06218P | A13 | | D05366P | 18 | | | 150-199 | | |

WIRE LIST

D280T132

91-21-11
Section W1710
Page 6 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1720 | 286T1720 | | | EICAS-E8 TO P54 | | | | | | | | | | | |
| 002R | 22 | | PH | | 24-0 | 26-11-11 | D06220P | A02 | \$D | | D05548P | | 2 | | ALL |
| 003R | 22 | | PH | | 24-0 | 26-11-12 | D06220P | A03 | \$D | | D05548P | | 3 | | ALL |
| 004R | 22 | | PH | | 24-0 | 26-11-21 | D06220P | A04 | \$D | | D05548P | | 4 | | ALL |
| 005R | 22 | | PH | | 24-0 | 26-11-22 | D06220P | A05 | \$D | | D05548P | | 5 | | ALL |
| 006R | 22 | | PH | | 24-0 | 26-15-11 | D06220P | A06 | \$D | | D05548P | | 6 | | ALL |
| 007R | 22 | | PH | | 24-0 | 26-11-21 | D06220P | A07 | \$D | | D05548P | | 7 | | ALL |
| 008R | 22 | | PH | | 24-0 | 26-11-22 | D06220P | A08 | \$D | | D05548P | | 8 | | ALL |
| 009R | 22 | | PH | | 24-0 | 26-15-11 | D06220P | A09 | \$D | | D05548P | | 9 | | ALL |
| 010 | 24 | | PK | | 24-0 | SPARE | D06220P | A10 | \$D | | D05548P | | 10 | | ALL |
| 011 | 24 | | PK | | 24-0 | SPARE | D06220P | A11 | \$D | | D05548P | | 11 | | ALL |
| 012R | 24 | | PP | | 24-0 | 26-16-11 | D06220P | A12 | \$D | | D05548P | | 12 | | ALL |
| 013R | 24 | | PP | | 24-0 | 26-16-11 | D06220P | A13 | \$D | | D05548P | | 13 | | ALL |
| 014R | 24 | | PP | | 24-0 | 26-16-11 | D06220P | A14 | \$D | | D05548P | | 14 | | ALL |
| 015R | 22 | | PH | | 24-0 | 26-17-11 | D06220P | A15 | \$D | | D05548P | | 15 | | ALL |
| 016 | 24 | | PK | | 1-0 | SPARE | D06220P | A16 | \$D | | D06220P | CAP | Y | | ALL |
| 017 | 24 | | PK | | 1-0 | SPARE | D06220P | A17 | \$D | | D06220P | CAP | Y | | ALL |
| 018 | 24 | | PK | | 1-0 | SPARE | D06220P | A18 | \$D | | D06220P | CAP | Y | | ALL |
| 019 | 24 | | PK | | 1-0 | SPARE | D06220P | A19 | \$D | | D06220P | CAP | Y | | ALL |
| W1722 | 286T1722 | | | EICAS-E8 TO E2-4,P34,P37 | | | | | | | | | | | |
| 002 | 24 | | PK | | 21-0 | 24-27-41 | D06222P | A02 | \$D | | D05340P | | 2 | | ALL |
| 003 | 24 | | PK | | 21-0 | 24-28-11 | D06222P | A03 | \$D | | D05340P | | 3 | | ALL |
| 004 | 24 | | PK | | 21-0 | 24-28-11 | D06222P | A04 | \$D | | D05340P | | 4 | | ALL |
| 005 | 24 | | PK | | 21-0 | 49-71-11 | D06222P | A05 | \$D | | D05340P | | 5 | | ALL |
| 006 | 24 | | PK | | 21-0 | SPARE | D06222P | A06 | \$D | | D05340P | | 6 | | 050-099 |
| 006 | 24 | | PK | | 2-0 | 49-94-11 | D06222P | A06 | \$D | | D06222P | CAP | Y | | 150-199 |
| 006 | 24 | | PK | | 1-0 | SPARE | D06222P | A06 | \$D | | D06222P | CAP | Y | | 275-299 |
| 007 | 24 | | PK | | 21-0 | 49-73-11 | D06222P | A07 | \$D | | D05340P | | 7 | | ALL |
| 008 | 24 | | PK | | 21-0 | SPARE | D06222P | A08 | \$D | | D05340P | | 8 | | ALL |
| 009 | 24 | | PK | | 21-0 | 24-34-11 | D06222P | A09 | \$D | | D05340P | | 9 | | ALL |
| 012 | 24 | | PK | | 21-0 | SPARE | D06222P | A12 | \$D | | D05206J | | 2 | | ALL |
| 013 | 24 | | PK | | 21-0 | 24-28-21 | D06222P | A13 | \$D | | D05206J | | 3 | | ALL |
| 014 | 24 | | PK | | 21-0 | 24-28-21 | D06222P | A14 | \$D | | D05206J | | 4 | | ALL |
| 015 | 24 | | PK | | 21-0 | 24-28-21 | D06222P | A15 | \$D | | D05206J | | 5 | | ALL |
| 016 | 24 | | PK | | 21-0 | SPARE | D06222P | A16 | \$D | | D05206J | | 6 | | ALL |
| 017 | 24 | | PK | | 21-0 | SPARE | D06222P | A17 | \$D | | D05206J | | 7 | | ALL |
| 018 | 24 | | PK | | 1-0 | SPARE | D06222P | A18 | \$D | | D06222P | CAP | Y | | ALL |
| 019 | 24 | | PK | | 1-0 | SPARE | D06222P | A19 | \$D | | D06222P | CAP | Y | | 050-099 |
| 019R | 22 | | PH | | 29-0 | SPARE | D06222P | A19 | \$D | | D05378P | | 1 | | 150-199 |

WIRE LIST

D280T132

91-21-11

Section W1720

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1722 | 286T1722 | | | EICAS-E8 TO E2-4,P34,P37 (continued) | | | | | | | | | | | |
| 019R | 22 | | PH | | 29-0 | 26-22-21 | D06222P | A19 | \$D | | D05378P | 1 | | | 275-299 |
| 022R | 22 | | PH | | 25-0 | 26-21-11 | D06222P | B02 | \$D | | D05378P | 2 | | | ALL |
| 023 | 24 | | PK | | 25-0 | 26-16-21 | D06222P | B03 | \$D | | D05378P | 3 | | | ALL |
| 024 | 24 | | PK | | 25-0 | 28-25-21 | D06222P | B04 | \$D | | D05378P | 4 | | | ALL |
| 026 | 24 | | PK | | 25-0 | SPARE | D06222P | B06 | \$D | | D05378P | 6 | | | ALL |
| 027 | 24 | | PK | | 25-0 | 36-11-41 | D06222P | B07 | \$D | | D05378P | 7 | | | ALL |
| 028 | 24 | | PK | | 25-0 | 49-61-11 | D06222P | B08 | \$D | | D05378P | 8 | | | ALL |
| 029 | 24 | | PK | | 25-0 | 49-61-11 | D06222P | B09 | \$D | | D05378P | 9 | | | ALL |
| 030R | 22 | | PH | | 25-0 | 26-22-21 | D06222P | B10 | \$D | | D05378P | 10 | | | ALL |
| 031R | 22 | | PH | | 25-0 | 26-23-11 | D06222P | B11 | \$D | | D05378P | 11 | | | ALL |
| 032 | 24 | | PK | | 25-0 | 49-15-11 | D06222P | B12 | \$D | | D05378P | 12 | | | ALL |
| 033 | 24 | | PK | | 2-0 | SPARE | D06222P | B13 | \$D | | D06222P | CAP | Y | | 150-199 |
| 034 | 24 | | PK | | 2-0 | SPARE | D06222P | B14 | \$D | | D06222P | CAP | Y | | 150-199 |
| 035 | 24 | | PK | | 25-0 | SPARE | D06222P | B15 | \$D | | D05378P | 15 | | | ALL |
| 036 | 24 | | PK | | 1-0 | SPARE | D06222P | B16 | \$D | | D06222P | CAP | Y | | ALL |
| 201B | 24 | | PL | IA | 21-0 | 24-34-11 | D06222P | A11 | \$D | | D05340P | 11 | | | ALL |
| 201R | 24 | | PL | IA | 0-0 | 24-34-11 | D06222P | A10 | \$D | | D05340P | 10 | | | ALL |
| 203B | 24 | | PL | IC | 25-0 | SPARE | D06222P | B13 | \$D | | D05378P | 13 | | | 050-099 |
| 203B | 24 | | PL | IC | 1-0 | SPARE | D06222P | B13 | \$D | | D06222P | CAP | Y | | 275-299 |
| 203R | 24 | | PL | IC | 0-0 | SPARE | D06222P | B14 | \$D | | D05378P | 14 | | | 050-099 |
| 203R | 24 | | PL | IC | 0-0 | SPARE | D06222P | B14 | \$D | | D06222P | CAP | Y | | 275-299 |
| 204B | 24 | | PW | ID | 21-0 | 31-41-35 | D06222P | B18 | \$D | | D05206J | 8 | | | ALL |
| 204R | 24 | | PW | ID | 0-0 | 31-41-35 | D06222P | B19 | \$D | | D05206J | 9 | | | ALL |
| 204Z | | | | ID | 0-0 | 31-41-35 | D06222P | | | FC | D05206J | 10 | | | ALL |
| FRC | | | | | 0-0 | 31-41-35 | D06222P | | | FC | D06222P | B17 | \$D | | ALL |
| FRD | | | | | 0-0 | 31-41-35 | D06222P | | | FC | D06222P | B20 | \$D | | ALL |
| W1724 | 286T1724 | | | *PCAS-E8 TO E1 | | | | | | | | | | | |
| 002 | 24 | | PK | | 15-0 | 32-61-14 | D06224P | A02 | \$D | | D05122J | 2 | | | ALL |
| 004 | 24 | | PK | | 15-0 | SPARE | D06224P | A04 | \$D | | D05122J | 4 | | | 050-099 |
| 004 | 24 | | PK | | 15-0 | 32-71-11 | D06224P | A04 | \$D | | D05122J | 4 | | | 150-199, 275-299 |
| 005 | 24 | | PK | | 15-0 | 32-61-14 | D06224P | A05 | \$D | | D05122J | 5 | | | ALL |
| 006 | 24 | | PK | | 15-0 | 32-61-14 | D06224P | A06 | \$D | | D05122J | 6 | | | ALL |
| 007 | 24 | | PK | | 15-0 | 32-61-14 | D06224P | A07 | \$D | | D05122J | 7 | | | ALL |
| 008 | 24 | | PK | | 15-0 | 32-61-14 | D06224P | A08 | \$D | | D05122J | 8 | | | ALL |
| 009 | 24 | | PK | | 15-0 | 32-61-14 | D06224P | A09 | \$D | | D05122J | 9 | | | ALL |
| 010 | 24 | | PK | | 15-0 | 32-61-14 | D06224P | A10 | \$D | | D05122J | 10 | | | ALL |
| 011 | 24 | | PK | | 15-0 | 32-61-14 | D06224P | A11 | \$D | | D05122J | 11 | | | ALL |
| 012 | 24 | | PK | | 15-0 | SPARE | D06224P | A12 | \$D | | D05122J | 12 | | | 050-099 |

WIRE LIST
D280T132

91-21-11
Section W1720
Page 2
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|-------|---------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1724 | 286T1724 | | | *PCAS-E8 TO E1 (continued) | | | | | | | | | | | | |
| 012 | 24 | | PK | 15-0 | 52-71-12 | D06224P | A12 | \$D | | D05122J | 12 | | | 150-199, 275-299 | | |
| 013 | 24 | | PK | 15-0 | SPARE | D06224P | A13 | \$D | | D05122J | 13 | | | 050-099 | | |
| 013 | 24 | | PK | 15-0 | 52-71-12 | D06224P | A13 | \$D | | D05122J | 13 | | | 150-199, 275-299 | | |
| 014 | 24 | | PK | 15-0 | 78-36-21 | D06224P | A14 | \$D | | D05122J | 14 | | | ALL | | |
| 015 | 24 | | PK | 15-0 | 78-36-21 | D06224P | A15 | \$D | | D05122J | 15 | | | ALL | | |
| 016 | 24 | | PK | 15-0 | 32-61-14 | D06224P | A16 | \$D | | D05122J | 16 | | | ALL | | |
| 017 | 24 | | PK | 15-0 | 32-61-14 | D06224P | A17 | \$D | | D05122J | 17 | | | ALL | | |
| 018 | 24 | | PK | 15-0 | 32-61-14 | D06224P | A18 | \$D | | D05122J | 18 | | | ALL | | |
| 019 | 24 | | PK | 15-0 | SPARE | D06224P | A19 | \$D | | D05122J | 19 | | | ALL | | |
| 022 | 24 | | PK | 15-0 | 52-71-11 | D06224P | B02 | \$D | | D05122J | 22 | | | ALL | | |
| 023 | 24 | | PK | 15-0 | 52-71-11 | D06224P | B03 | \$D | | D05122J | 23 | | | ALL | | |
| 024 | 24 | | PK | 15-0 | 52-71-13 | D06224P | B04 | \$D | | D05122J | 24 | | | ALL | | |
| 025 | 24 | | PK | 15-0 | 52-71-11 | D06224P | B05 | \$D | | D05122J | 25 | | | ALL | | |
| 026 | 24 | | PK | 15-0 | 52-71-11 | D06224P | B06 | \$D | | D05122J | 26 | | | ALL | | |
| 027 | 24 | | PK | 15-0 | 52-71-12 | D06224P | B07 | \$D | | D05122J | 27 | | | ALL | | |
| 028 | 24 | | PK | 15-0 | 52-71-12 | D06224P | B08 | \$D | | D05122J | 28 | | | ALL | | |
| 029 | 24 | | PK | 15-0 | 52-71-12 | D06224P | B09 | \$D | | D05122J | 29 | | | ALL | | |
| 030 | 24 | | PK | 15-0 | 52-71-12 | D06224P | B10 | \$D | | D05122J | 30 | | | ALL | | |
| 031 | 24 | | PK | 15-0 | 52-71-14 | D06224P | B11 | \$D | | D05122J | 31 | | | ALL | | |
| 032 | 24 | | PK | 15-0 | 52-71-14 | D06224P | B12 | \$D | | D05122J | 32 | | | ALL | | |
| 033 | 24 | | PK | 15-0 | 52-71-13 | D06224P | B13 | \$D | | D05122J | 33 | | | ALL | | |
| 034 | 24 | | PK | 15-0 | 52-71-13 | D06224P | B14 | \$D | | D05122J | 34 | | | ALL | | |
| 035 | 24 | | PK | 15-0 | 27-88-11 | D06224P | B15 | \$D | | D05122J | 35 | | | ALL | | |
| 036 | 24 | | PK | 15-0 | 27-88-11 | D06224P | B16 | \$D | | D05122J | 36 | | | ALL | | |
| 037 | 24 | | PK | 15-0 | SPARE | D06224P | B17 | \$D | | D05122J | 37 | | | ALL | | |
| 038 | 24 | | PK | 15-0 | SPARE | D06224P | B18 | \$D | | D05122J | 38 | | | ALL | | |
| 039 | 24 | | PK | 15-0 | SPARE | D06224P | B19 | \$D | | D05122J | 39 | | | ALL | | |
| W1725 | 286T1725 | | | CCA-C, E1-4 SHELF TO R WW DISC | | | | | | | | | | | | |
| 001 | 20 | | PA | 66-0 | 22-11-32 | D04405J | 11 | | | D04675J | 11 | | | 050-099 | | |
| 001 | 20 | | PA | 76-0 | 22-11-32 | D04405J | 11 | | | D04675J | 11 | | | 150-199, 275-299 | | |
| 002 | 20 | | PA | 66-0 | 22-11-32 | D04405J | 14 | | | D04675J | 14 | | | 050-099 | | |
| 002 | 20 | | PA | 76-0 | 22-11-32 | D04405J | 14 | | | D04675J | 14 | | | 150-199, 275-299 | | |
| 201B | 20 | | PB IA | 66-0 | 22-11-31 | D04405J | 2 | | | D04675J | 2 | | | 050-099 | | |
| 201B | 20 | | PB IA | 76-0 | 22-11-31 | D04405J | 2 | | | D04675J | 2 | | | 150-199, 275-299 | | |
| 201R | 20 | | PB IA | 0-0 | 22-11-31 | D04405J | 1 | | | D04675J | 1 | | | ALL | | |
| 202B | 20 | | PB IB | 66-0 | 22-13-31 | D04405J | 4 | | | D04675J | 4 | | | 050-099 | | |
| 202B | 20 | | PB IB | 76-0 | 22-13-31 | D04405J | 4 | | | D04675J | 4 | | | 150-199, 275-299 | | |
| 202R | 20 | | PB IB | 0-0 | 22-13-31 | D04405J | 3 | | | D04675J | 3 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W1720

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1725 | 286T1725 | | | CCA-C, E1-4 SHELF TO R WW DISC (continued) | | | | | | | | | | | |
| 301B | 20 | PC | MA | 66-0 | 22-13-31 | D04405J | | 6 | | | D04675J | | 6 | | 050-099 |
| 301B | 20 | PC | MA | 76-0 | 22-13-31 | D04405J | | 6 | | | D04675J | | 6 | | 150-199, 275-299 |
| 301R | 20 | PC | MA | 0-0 | 22-13-31 | D04405J | | 5 | | | D04675J | | 5 | | ALL |
| 301Y | 20 | PC | MA | 0-0 | 22-13-31 | D04405J | | 7 | | | D04675J | | 7 | | ALL |
| 302B | 20 | PC | MB | 66-0 | 22-13-31 | D04405J | | 9 | | | D04675J | | 9 | | 050-099 |
| 302B | 20 | PC | MB | 76-0 | 22-13-31 | D04405J | | 9 | | | D04675J | | 9 | | 150-199, 275-299 |
| 302R | 20 | PC | MB | 0-0 | 22-13-31 | D04405J | | 8 | | | D04675J | | 8 | | ALL |
| 302Y | 20 | PC | MB | 0-0 | 22-13-31 | D04405J | | 10 | | | D04675J | | 10 | | ALL |
| W1726 | 286T1726 | | | EICAS-E8 TO E2-4 | | | | | | | | | | | |
| 002 | 24 | PK | | 25-0 | 28-41-11 | D06226P | | A02 | \$D | | D05202J | | 2 | | ALL |
| 003 | 24 | PK | | 25-0 | 27-51-41 | D06226P | | A03 | \$D | | D05202J | | 3 | | ALL |
| 004 | 24 | PK | | 25-0 | 27-51-51 | D06226P | | A04 | \$D | | D05202J | | 4 | | ALL |
| 005 | 24 | PK | | 25-0 | 27-58-31 | D06226P | | A05 | \$D | | D05202J | | 5 | | ALL |
| 010 | 24 | PK | | 25-0 | 32-46-11 | D06226P | | A10 | \$D | | D05202J | | 10 | | ALL |
| 011 | 24 | PK | | 25-0 | 32-46-11 | D06226P | | A11 | \$D | | D05202J | | 11 | | ALL |
| 012 | 24 | PK | | 25-0 | 32-46-11 | D06226P | | A12 | \$D | | D05202J | | 12 | | ALL |
| 013 | 24 | PK | | 25-0 | 32-46-11 | D06226P | | A13 | \$D | | D05202J | | 13 | | ALL |
| 014 | 24 | PK | | 25-0 | 32-46-11 | D06226P | | A14 | \$D | | D05202J | | 14 | | ALL |
| 015 | 24 | PK | | 25-0 | 32-46-11 | D06226P | | A15 | \$D | | D05202J | | 15 | | ALL |
| 016 | 24 | PK | | 25-0 | 32-46-11 | D06226P | | A16 | \$D | | D05202J | | 16 | | ALL |
| 017 | 24 | PK | | 25-0 | 32-46-11 | D06226P | | A17 | \$D | | D05202J | | 17 | | ALL |
| 018 | 24 | PK | | 25-0 | 32-46-11 | D06226P | | A18 | \$D | | D05202J | | 18 | | ALL |
| 019 | 24 | PK | | 25-0 | 28-41-13 | D06226P | | A19 | \$D | | D05202J | | 19 | | ALL |
| 201B | 24 | PW | IA | 25-0 | 77-31-11 | D06226P | | A08 | \$D | | D05202J | | 8 | | ALL |
| 201R | 24 | PW | IA | 0-0 | 77-31-11 | D06226P | | A07 | \$D | | D05202J | | 7 | | ALL |
| 201Z | | | IA | 0-0 | 77-31-11 | D06226P | | | | FA | D05202J | | 9 | | ALL |
| FRA | | | | 0-0 | 77-31-11 | D06226P | | A06 | \$D | | D06226P | | | FA | ALL |
| FRB | | | | 0-0 | 77-31-11 | D06226P | | A09 | \$D | | D06226P | | | FA | ALL |
| W1727 | 286T1727 | | | CCA-C, R WW DISC TO CCA-C | | | | | | | | | | | |
| 001 | 18 | UA | | 3-7 | 22-11-32 | GD00147 | | D.. | N | | D00193 | | 1 | | ALL |
| 002 | 20 | UA | | 10-0 | 22-11-32 | D04675P | | 11 | | | D00193 | | 2 | | ALL |
| 003 | 18 | UA | | 3-7 | 22-11-32 | GD00147 | | D.. | N | | D00193 | | 17 | | ALL |
| 004 | 20 | UA | | 10-0 | 22-11-32 | D04675P | | 14 | | | D00193 | | 18 | | ALL |
| 019 | 18 | UA | | 3-7 | 22-11-32 | GD00149 | | S.. | N | | D00193 | | 19 | | ALL |
| 201B | 20 | UB | IA | 10-0 | 22-11-31 | D04675P | | 2 | | | SM00002 | | 9 | | ALL |
| 201R | 20 | UB | IA | 0-0 | 22-11-31 | D04675P | | 1 | | | SM00001 | | 9 | | ALL |
| 202B | 20 | UB | IB | 0-6 | 22-11-31 | SM00002 | | | | 9 | D00193 | | 12 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1720
Page 4
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1727 | 286T1727 | | | CCA-C, R WW DISC TO CCA-C (continued) | | | | | | | | | | | | |
| 202R | 20 | UB | IB | 0-0 | 22-11-31 | SM00001 | | | 9 | | D00193 | 13 | | | ALL | |
| 203B | 20 | UB | IC | 0-6 | 22-11-31 | SM00002 | | | 9 | | D00193 | 7 | | | ALL | |
| 203R | 20 | UB | IC | 0-0 | 22-11-31 | SM00001 | | | 9 | | D00193 | 8 | | | ALL | |
| 204B | 20 | UB | ID | 10-0 | 22-13-31 | D04675P | | 4 | | | SM00004 | | 9 | | ALL | |
| 204R | 20 | UB | ID | 0-0 | 22-13-31 | D04675P | | 3 | | | SM00003 | | 9 | | ALL | |
| 205B | 20 | UB | IE | 0-6 | 22-13-31 | SM00004 | | | 9 | | D00193 | 6 | | | ALL | |
| 205R | 20 | UB | IE | 0-0 | 22-13-31 | SM00003 | | | 9 | | D00193 | 5 | | | ALL | |
| 206B | 20 | UB | IF | 0-6 | 22-13-31 | SM00004 | | | 9 | | D00193 | 4 | | | ALL | |
| 206R | 20 | UB | IF | 0-0 | 22-13-31 | SM00003 | | | 9 | | D00193 | 3 | | | ALL | |
| 301B | 20 | UC | MA | 10-0 | 22-13-31 | D04675P | | 6 | | | D00193 | 15 | | | ALL | |
| 301R | 20 | UC | MA | 0-0 | 22-13-31 | D04675P | | 5 | | | D00193 | 16 | | | ALL | |
| 301Y | 20 | UC | MA | 0-0 | 22-13-31 | D04675P | | 7 | | | D00193 | 14 | | | ALL | |
| 302B | 20 | UC | MB | 10-0 | 22-13-31 | D04675P | | 9 | | | D00193 | 10 | | | ALL | |
| 302R | 20 | UC | MB | 0-0 | 22-13-31 | D04675P | | 8 | | | D00193 | 11 | | | ALL | |
| 302Y | 20 | UC | MB | 0-0 | 22-13-31 | D04675P | | 10 | | | D00193 | 9 | | | ALL | |
| W1728 | 286T1728 | | | EICAS-E8 TO E1-2 | | | | | | | | | | | | |
| 002 | 24 | PK | | 15-0 | 32-61-14 | D06228P | | A02 | \$D | | D05140J | 2 | | | ALL | |
| 003 | 24 | PK | | 15-0 | SPARE | D06228P | | A03 | \$D | | D05140J | 3 | | | ALL | |
| 004 | 24 | PK | | 15-0 | SPARE | D06228P | | A04 | \$D | | D05140J | 4 | | | ALL | |
| 005 | 24 | PK | | 15-0 | 32-61-14 | D06228P | | A05 | \$D | | D05140J | 5 | | | ALL | |
| 006 | 24 | PK | | 15-0 | 32-61-14 | D06228P | | A06 | \$D | | D05140J | 6 | | | ALL | |
| 007 | 24 | PK | | 15-0 | 32-61-14 | D06228P | | A07 | \$D | | D05140J | 7 | | | ALL | |
| 008 | 24 | PK | | 15-0 | 32-61-14 | D06228P | | A08 | \$D | | D05140J | 8 | | | ALL | |
| 009 | 24 | PK | | 15-0 | 32-61-14 | D06228P | | A09 | \$D | | D05140J | 9 | | | ALL | |
| 010 | 24 | PK | | 15-0 | 32-61-14 | D06228P | | A10 | \$D | | D05140J | 10 | | | ALL | |
| 011 | 24 | PK | | 15-0 | 32-61-14 | D06228P | | A11 | \$D | | D05140J | 11 | | | ALL | |
| 012 | 24 | PK | | 15-0 | 32-61-14 | D06228P | | A12 | \$D | | D05140J | 12 | | | ALL | |
| 013 | 24 | PK | | 15-0 | SPARE | D06228P | | A13 | \$D | | D05140J | 13 | | | ALL | |
| 014 | 24 | PK | | 15-0 | SPARE | D06228P | | A14 | \$D | | D05140J | 14 | | | ALL | |
| 015 | 24 | PK | | 1-0 | SPARE | D06228P | | A15 | \$D | | D06228P | | CAP | Y | ALL | |
| 016 | 24 | PK | | 1-0 | SPARE | D06228P | | A16 | \$D | | D06228P | | CAP | Y | ALL | |
| 202B | 24 | PW | IB | 15-0 | 77-12-12 | D06228P | | A18 | \$D | | D05140J | 18 | | | ALL | |
| 202R | 24 | PW | IB | 0-0 | 77-12-12 | D06228P | | A19 | \$D | | D05140J | 19 | | | ALL | |
| 202Z | | | IB | 0-0 | 77-12-12 | D06228P | | A17 | \$D | | D05140J | 17 | | | ALL | |
| W1729 | 286T1729 | | | CCA-R, E1-5 SHELF TO L WW DISC | | | | | | | | | | | | |
| 001 | 20 | PA | | 76-0 | 22-11-22 | D04529J | | | 11 | | D04677J | 11 | | | 050-099 | |
| 001 | 20 | PA | | 85-0 | 22-11-22 | D04529J | | | 11 | | D04677J | 11 | | | 150-199, 275-299 | |

WIRE LIST
D280T132

91-21-11
Section W1720
Page 5
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1729 | 286T1729 | | | CCA-R, E1-5 SHELF TO L WW DISC (continued) | | | | | | | | | | | |
| 002 | 20 | | PA | 76-0 | 22-11-22 | D04529J | | 14 | | D04677J | | 14 | | 050-099 | |
| 002 | 20 | | PA | 85-0 | 22-11-22 | D04529J | | 14 | | D04677J | | 14 | | 150-199, 275-299 | |
| 201B | 20 | | PB IA | 76-0 | 22-11-21 | D04529J | | 2 | | D04677J | | 2 | | 050-099 | |
| 201B | 20 | | PB IA | 85-0 | 22-11-21 | D04529J | | 2 | | D04677J | | 2 | | 150-199, 275-299 | |
| 201R | 20 | | PB IA | 0-0 | 22-11-21 | D04529J | | 1 | | D04677J | | 1 | | ALL | |
| 202B | 20 | | PB IB | 76-0 | 22-13-21 | D04529J | | 4 | | D04677J | | 4 | | 050-099 | |
| 202B | 20 | | PB IB | 85-0 | 22-13-21 | D04529J | | 4 | | D04677J | | 4 | | 150-199, 275-299 | |
| 202R | 20 | | PB IB | 0-0 | 22-13-21 | D04529J | | 3 | | D04677J | | 3 | | ALL | |
| 301B | 20 | | PC MA | 76-0 | 22-13-21 | D04529J | | 6 | | D04677J | | 6 | | 050-099 | |
| 301B | 20 | | PC MA | 85-0 | 22-13-21 | D04529J | | 6 | | D04677J | | 6 | | 150-199, 275-299 | |
| 301R | 20 | | PC MA | 0-0 | 22-13-21 | D04529J | | 5 | | D04677J | | 5 | | ALL | |
| 301Y | 20 | | PC MA | 0-0 | 22-13-21 | D04529J | | 7 | | D04677J | | 7 | | ALL | |
| 302B | 20 | | PC MB | 76-0 | 22-13-21 | D04529J | | 9 | | D04677J | | 9 | | 050-099 | |
| 302B | 20 | | PC MB | 85-0 | 22-13-21 | D04529J | | 9 | | D04677J | | 9 | | 150-199, 275-299 | |
| 302R | 20 | | PC MB | 0-0 | 22-13-21 | D04529J | | 8 | | D04677J | | 8 | | ALL | |
| 302Y | 20 | | PC MB | 0-0 | 22-13-21 | D04529J | | 10 | | D04677J | | 10 | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W1720
Page 6 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1730 | 286T1730 | | | EICAS-E8 TO P33 | | | | | | | | | | | |
| 002 | 24 | | PK | | 20-0 | 78-36-21 | D06230P | A02 | \$D | | D05334P | 2 | | | ALL |
| 003 | 24 | | PK | | 20-0 | 30-31-11 | D06230P | A03 | \$D | | D05334P | 3 | | | ALL |
| 004 | 24 | | PK | | 20-0 | 30-31-11 | D06230P | A04 | \$D | | D05334P | 4 | | | ALL |
| 005 | 24 | | PK | | 20-0 | 30-31-13 | D06230P | A05 | \$D | | D05334P | 5 | | | ALL |
| 006 | 24 | | PK | | 20-0 | 30-31-13 | D06230P | A06 | \$D | | D05334P | 6 | | | ALL |
| 007 | 24 | | PK | | 20-0 | 30-32-11 | D06230P | A07 | \$D | | D05334P | 7 | | | ALL |
| 008 | 24 | | PK | | 2-0 | SPARE | D06230P | A08 | \$D | | D06230P | CAP | Y | | 150-199 |
| 008 | 24 | | PK | | 1-0 | SPARE | D06230P | A08 | \$D | | D06230P | CAP | Y | | 275-299 |
| 009 | 24 | | PK | | 20-0 | 30-33-11 | D06230P | A09 | \$D | | D05334P | 9 | | | ALL |
| 010 | 24 | | PK | | 2-0 | SPARE | D06230P | A10 | \$D | | D06230P | CAP | Y | | 150-199 |
| 010 | 24 | | PK | | 20-0 | SPARE | D06230P | A10 | \$D | | D05334P | 10 | | | 275-299 |
| 011 | 24 | | PK | | 20-0 | 28-42-11 | D06230P | A11 | \$D | | D05334P | 11 | | | ALL |
| 012 | 24 | | PK | | 20-0 | 30-11-11 | D06230P | A12 | \$D | | D05334P | 12 | | | ALL |
| 013 | 24 | | PK | | 20-0 | 30-11-11 | D06230P | A13 | \$D | | D05334P | 13 | | | ALL |
| 014 | 24 | | PK | | 20-0 | 30-11-11 | D06230P | A14 | \$D | | D05334P | 14 | | | ALL |
| 015 | 24 | | PK | | 20-0 | 30-11-11 | D06230P | A15 | \$D | | D05334P | 15 | | | ALL |
| 016 | 24 | | PK | | 20-0 | 21-44-21 | D06230P | A16 | \$D | | D05334P | 16 | | | ALL |
| 017 | 24 | | PK | | 20-0 | 28-42-12 | D06230P | A17 | \$D | | D05334P | 17 | | | ALL |
| 018 | 24 | | PK | | 20-0 | 27-51-11 | D06230P | A18 | \$D | | D05334P | 18 | | | ALL |
| 019 | 24 | | PK | | 20-0 | SPARE | D06230P | A19 | \$D | | D05334P | 19 | | | ALL |
| 022 | 22 | | PA | | 20-0 | 30-81-11 | D05334P | 20 | | | D06230P | B02 | \$D | | 050-099, 150-199 |
| 023 | 22 | | PA | | 20-0 | 30-81-11 | D05334P | 21 | | | D06230P | B03 | \$D | | 050-099, 150-199 |
| 024 | 24 | | PV | Z | 20-0 | 28-22-31 | D06230P | B04 | \$D | | D05334P | 23 | | | ALL |
| 024Z | | | | Z | 0-0 | 28-22-31 | D06230P | DED | | | D05334P | DED | | | ALL |
| 025 | 24 | | PV | Y | 24-0 | 28-22-31 | D06230P | B05 | \$D | | D05334P | 24 | | | ALL |
| 025Z | | | | Y | 0-0 | 28-22-31 | D06230P | DED | | | D05334P | DED | | | ALL |
| 026 | 22 | | PA | | 2-0 | SPARE | D06230P | B06 | \$D | | D06230P | CAP | Y | | 150-154 |
| 027 | 22 | | PA | | 2-0 | SPARE | D06230P | B07 | \$D | | D06230P | CAP | Y | | 150-154 |
| 028 | 22 | | PA | | 2-0 | SPARE | D06230P | B08 | \$D | | D06230P | CAP | Y | | 150-154 |
| 029 | 22 | | PA | | 2-0 | SPARE | D06230P | B09 | \$D | | D06230P | CAP | Y | | 150-154 |
| 030 | 22 | | PA | | 2-0 | SPARE | D06230P | B10 | \$D | | D06230P | CAP | Y | | 150-154 |
| 031 | 22 | | PA | | 2-0 | SPARE | D06230P | B11 | \$D | | D06230P | CAP | Y | | 150-154 |
| 032 | 22 | | PA | | 2-0 | SPARE | D06230P | B12 | \$D | | D06230P | CAP | Y | | 150-154 |
| 033 | 22 | | PA | | 2-0 | SPARE | D06230P | B13 | \$D | | D06230P | CAP | Y | | 150-154 |
| 034 | 22 | | PA | | 2-0 | SPARE | D06230P | B14 | | | D06230P | CAP | Y | | 150-154 |
| 035 | 22 | | PA | | 2-0 | SPARE | D06230P | B15 | \$D | | D06230P | CAP | Y | | 150-154 |
| 036 | 22 | | PA | | 2-0 | SPARE | D06230P | B16 | \$D | | D06230P | CAP | Y | | 150-154 |
| 037 | 22 | | PA | | 2-0 | SPARE | D06230P | B17 | \$D | | D06230P | CAP | Y | | 150-154 |
| 038 | 22 | | PA | | 2-0 | SPARE | D06230P | B18 | \$D | | D06230P | CAP | Y | | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W1730

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1730 | 286T1730 | | | EICAS-E8 TO P33 (continued) | | | | | | | | | | | |
| 039 | 22 | | PA | | 2-0 | SPARE | D06230P | B19 | \$D | | D06230P | CAP | Y | | 150-154 |
| W1731 | 286T1731 | | | CCA-R, L WW DISC TO CCA-R | | | | | | | | | | | |
| 001 | 18 | | UA | | 3-2 | 22-11-22 | GD00181 | D.. | N | | D00201 | | 1 | | ALL |
| 002 | 20 | | UA | | 13-7 | 22-11-22 | D04677P | 11 | | | D00201 | | 2 | | ALL |
| 003 | 18 | | UA | | 3-2 | 22-11-22 | GD00181 | D.. | N | | D00201 | | 17 | | ALL |
| 004 | 20 | | UA | | 13-7 | 22-11-22 | D04677P | 14 | | | D00201 | | 18 | | ALL |
| 019 | 18 | | UA | | 2-0 | 22-11-22 | GD04056 | S.. | N | | D00201 | | 19 | | ALL |
| 201B | 20 | | UB | IA | 14-0 | 22-11-21 | D04677P | 2 | | | SM00002 | | 9 | | ALL |
| 201R | 20 | | UB | IA | 0-0 | 22-11-21 | D04677P | 1 | | | SM00001 | | 9 | | ALL |
| 202B | 20 | | UB | IB | 0-8 | 22-11-21 | SM00002 | | 9 | | D00201 | | 12 | | ALL |
| 202R | 20 | | UB | IB | 0-0 | 22-11-21 | SM00001 | | 9 | | D00201 | | 13 | | ALL |
| 203B | 20 | | UB | IC | 0-8 | 22-11-21 | SM00002 | | 9 | | D00201 | | 7 | | ALL |
| 203R | 20 | | UB | IC | 0-0 | 22-11-21 | SM00001 | | 9 | | D00201 | | 8 | | ALL |
| 204B | 20 | | UB | ID | 14-0 | 22-13-21 | D04677P | 4 | | | SM00004 | | 9 | | ALL |
| 204R | 20 | | UB | ID | 0-0 | 22-13-21 | D04677P | 3 | | | SM00003 | | 9 | | ALL |
| 205B | 20 | | UB | IE | 0-8 | 22-13-21 | SM00004 | | 9 | | D00201 | | 3 | | ALL |
| 205R | 20 | | UB | IE | 0-0 | 22-13-21 | SM00003 | | 9 | | D00201 | | 4 | | ALL |
| 206B | 20 | | UB | IF | 0-8 | 22-13-21 | SM00004 | | 9 | | D00201 | | 5 | | ALL |
| 206R | 20 | | UB | IF | 0-0 | 22-13-21 | SM00003 | | 9 | | D00201 | | 6 | | ALL |
| 301B | 20 | | UC | MA | 13-7 | 22-13-21 | D04677P | | 6 | | D00201 | | 15 | | ALL |
| 301R | 20 | | UC | MA | 0-0 | 22-13-21 | D04677P | | 5 | | D00201 | | 14 | | ALL |
| 301Y | 20 | | UC | MA | 0-0 | 22-13-21 | D04677P | | 7 | | D00201 | | 16 | | ALL |
| 302B | 20 | | UC | MB | 13-7 | 22-13-21 | D04677P | | 9 | | D00201 | | 10 | | ALL |
| 302R | 20 | | UC | MB | 0-0 | 22-13-21 | D04677P | | 8 | | D00201 | | 9 | | ALL |
| 302Y | 20 | | UC | MB | 0-0 | 22-13-21 | D04677P | | 10 | | D00201 | | 11 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W1730
Page 2 End
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|------|--|----------|---------|------|------|--------|---------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1769 | 286T1769 | | | | TCAS COAX-SHELF TO BOTTOM ANT.DISC. | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D06097J | = | C1 | | D06095J | = | C1 | 050-099, 150-199, 277-299 | |
| 01CX | | | | XE A | 11-6 | 34-45-11 | D06097J | = | A1 | | D06095J | = | A1 | 050-099, 150-199, 277-299 | |
| 02CO | | | | B | 0-0 | 34-45-11 | D06127J | = | C1 | | D06133J | = | C1 | 050-099, 150-199, 277-299 | |
| 02CX | | | | XE B | 11-6 | 34-45-11 | D06127J | = | A1 | | D06133J | = | A1 | 050-099, 150-199, 277-299 | |
| 03CO | | | | C | 0-0 | 34-45-11 | D06129J | = | C1 | | D06135J | = | C1 | 050-099, 150-199, 277-299 | |
| 03CX | | | | XE C | 11-6 | 34-45-11 | D06129J | = | A1 | | D06135J | = | A1 | 050-099, 150-199, 277-299 | |
| 04CO | | | | D | 0-0 | 34-45-11 | D06131J | = | C1 | | D06137J | = | C1 | 050-099, 150-199, 277-299 | |
| 04CX | | | | XE D | 11-6 | 34-45-11 | D06131J | = | A1 | | D06137J | = | A1 | 050-099, 150-199, 277-299 | |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1771 | 286T1771 | | | | TCAS COAX-SHELF TO ANT.DISC. | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D06079J | = | C1 | | D06087J | = | C1 | | 050-099, 150-199, 277-299 |
| 01CX | | | JB | A | 28-0 | 34-45-11 | D06079J | = | A1 | | D06087J | = | A1 | | 050-099, 150-199, 277-299 |
| W1773 | 286T1773 | | | | COAX-TCAS SUPPRESSION | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-53-21 | D02541 | = | C1 | | D02543 | = | C1 | | ALL |
| 01CX | | | BR | A | 1-6 | 34-53-21 | D02541 | = | A1 | | D02543 | = | A1 | | ALL |
| W1775 | 286T1775 | | | | TCAS COAX-SHELF TO ANT.DISC. | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D06081J | = | C1 | | D06089J | = | C1 | | 050-099, 150-199, 277-299 |
| 01CX | | | JB | A | 28-0 | 34-45-11 | D06081J | = | A1 | | D06089J | = | A1 | | 050-099, 150-199, 277-299 |
| W1777 | 286T1777 | | | | TCAS COAX-SHELF TO ANT.DISC. | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D06083J | = | C1 | | D06091J | = | C1 | | 050-099, 150-199, 277-299 |
| 01CX | | | JB | A | 28-0 | 34-45-11 | D06083J | = | A1 | | D06091J | = | A1 | | 050-099, 150-199, 277-299 |
| W1779 | 286T1779 | | | | TCAS COAX-SHELF TO ANT.DISC. | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D06085J | = | C1 | | D06093J | = | C1 | | 050-099, 150-199, 277-299 |
| 01CX | | | JB | A | 28-0 | 34-45-11 | D06085J | = | A1 | | D06093J | = | A1 | | 050-099, 150-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W1770
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------|----------|--------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1791 | 286T1791 | | | | COAX-TCAS ANT.TO DISC. | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D02465 | = | C1 | | D06079P | = | C1 | | 050-099, 150-199, 277-299 |
| 01CX | | 78 | | A | 1-6 | 34-45-11 | D02465 | = | A1 | | D06079P | = | A1 | | 050-099, 150-199, 277-299 |
| W1795 | 286T1795 | | | | COAX-TCAS ANT.TO DISC. | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D02529 | = | C1 | | D06081P | = | C1 | | 050-099, 150-199, 277-299 |
| 01CX | | 78 | | A | 1-6 | 34-45-11 | D02529 | = | A1 | | D06081P | = | A1 | | 050-099, 150-199, 277-299 |
| W1797 | 286T1797 | | | | COAX-TCAS ANT.TO DISC. | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D02531 | = | C1 | | D06083P | = | C1 | | 050-099, 150-199, 277-299 |
| 01CX | | 78 | | A | 1-6 | 34-45-11 | D02531 | = | A1 | | D06083P | = | A1 | | 050-099, 150-199, 277-299 |
| W1799 | 286T1799 | | | | COAX-TCAS ANT.TO DISC. | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D02533 | = | C1 | | D06085P | = | C1 | | 050-099, 150-199, 277-299 |
| 01CX | | 78 | | A | 1-6 | 34-45-11 | D02533 | = | A1 | | D06085P | = | A1 | | 050-099, 150-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W1790
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|---|-------|------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1801 | 286T1801 | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | | |
| 001 | 20 | PA | | 33-0 | 23-32-31 | D02325 | | 1 | | | D02317 | | 1 | | 275-299 |
| 002 | 20 | PA | | 33-0 | 23-32-31 | D02325 | | 4 | | | D02317 | | 2 | | 275-299 |
| 003 | 22 | PA | | 33-0 | 23-32-31 | D02325 | | 2 | | | D02317 | | 10 | | 275-299 |
| 004 | 24 | PK | | 33-0 | 23-32-31 | D02325 | | 8 | | | D02317 | | 6 | | 275-299 |
| 005 | 22 | PA | | 33-0 | 23-32-31 | SM00001 | | | S | | D02317 | | 9 | | 275-299 |
| 006 | 22 | PA | | 2-0 | 23-32-31 | D02325 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | PA | | 2-0 | 23-32-31 | D02325 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | PA | | 2-0 | 23-32-31 | D02325 | | 6 | | | SM00001 | | | S | 275-299 |
| 009 | 22 | PA | | 2-0 | 23-32-31 | D02325 | | 7 | | | SM00001 | | | S | 275-299 |
| 01CO | | | A | 0-0 | 23-32-31 | D02483 | | | =C1 | | D02317 | | =C1 | | 275-299 |
| 01CX | | 5X | A | 33-0 | 23-32-31 | D02483 | | | =A1 | | D02317 | | =A1 | | 275-299 |
| W1803 | 286T1803 | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | | |
| 001 | 20 | PA | | 21-0 | 23-32-31 | D02327 | | 1 | | | D02319 | | 1 | | 275-299 |
| 002 | 20 | PA | | 21-0 | 23-32-31 | D02327 | | 4 | | | D02319 | | 2 | | 275-299 |
| 003 | 22 | PA | | 21-0 | 23-32-31 | D02327 | | 2 | | | D02319 | | 10 | | 275-299 |
| 004 | 24 | PK | | 21-0 | 23-32-31 | D02327 | | 8 | | | D02319 | | 6 | | 275-299 |
| 005 | 22 | PA | | 21-0 | 23-32-31 | SM00001 | | | S | | D02319 | | 9 | | 275-299 |
| 006 | 22 | PA | | 2-0 | 23-32-31 | D02327 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | PA | | 2-0 | 23-32-31 | D02327 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | PA | | 2-0 | 23-32-31 | D02327 | | 6 | | | SM00001 | | | S | 275-299 |
| 009 | 22 | PA | | 2-0 | 23-32-31 | D02327 | | 7 | | | SM00001 | | | S | 275-299 |
| 01CO | | | A | 0-0 | 23-32-31 | D02485 | | | =C1 | | D02319 | | =C1 | | 275-299 |
| 01CX | | 5X | A | 21-0 | 23-32-31 | D02485 | | | =A1 | | D02319 | | =A1 | | 275-299 |
| W1805 | 286T1805 | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | | |
| 001 | 20 | PA | | 36-0 | 23-32-32 | D02337 | | 1 | | | D02329 | | 1 | | 275-278 |
| 001 | 20 | PA | | 15-0 | 23-32-32 | D02337 | | 1 | | | D02329 | | 1 | | 280-299 |
| 002 | 20 | PA | | 36-0 | 23-32-32 | D02337 | | 4 | | | D02329 | | 2 | | 275-278 |
| 002 | 20 | PA | | 15-0 | 23-32-32 | D02337 | | 4 | | | D02329 | | 2 | | 280-299 |
| 003 | 22 | PA | | 36-0 | 23-32-32 | D02337 | | 2 | | | D02329 | | 10 | | 275-278 |
| 003 | 22 | PA | | 15-0 | 23-32-32 | D02337 | | 2 | | | D02329 | | 10 | | 280-299 |
| 004 | 24 | PK | | 36-0 | 23-32-32 | D02337 | | 8 | | | D02329 | | 6 | | 275-278 |
| 004 | 24 | PK | | 15-0 | 23-32-32 | D02337 | | 8 | | | D02329 | | 6 | | 280-299 |
| 005 | 22 | PA | | 36-0 | 23-32-32 | SM00001 | | | S | | D02329 | | 9 | | 275-278 |
| 005 | 22 | PA | | 26-0 | 23-32-32 | SM00001 | | | S | | D02329 | | 9 | | 280-299 |
| 006 | 22 | PA | | 2-0 | 23-32-32 | D02337 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | PA | | 2-0 | 23-32-32 | D02337 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | PA | | 2-0 | 23-32-32 | D02337 | | 6 | | | SM00001 | | | S | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1800

Page 1

Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|--|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1805 | 286T1805 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR (continued) | | | | | | | | | | | | |
| 009 | 22 | PA | | 2-0 | 23-32-32 | D02337 | | 7 | | | | SM00001 | | S | | 275-299 |
| 01CO | | | A | 0-0 | 23-32-32 | D02487 | | = C1 | | | | D02329 | | = C1 | | 275-278 |
| 01CO | | | A | 0-0 | 23-32-32 | D02337 | | = C1 | | | | D02329 | | = C1 | | 280-299 |
| 01CX | | 5X | A | 36-0 | 23-32-32 | D02487 | | = A1 | | | | D02329 | | = A1 | | 275-278 |
| 01CX | | 5X | A | 15-0 | 23-32-32 | D02337 | | = A1 | | | | D02329 | | = A1 | | 280-299 |
| W1807 | 286T1807 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | |
| 001 | 20 | PA | | 25-0 | 23-32-32 | D02491 | | 1 | | | | D02331 | | 1 | | 275-278 |
| 001 | 20 | PA | | 31-0 | 23-32-32 | D02491 | | 1 | | | | D02331 | | 1 | | 280-299 |
| 002 | 20 | PA | | 25-0 | 23-32-32 | D02491 | | 4 | | | | D02331 | | 2 | | 275-278 |
| 002 | 20 | PA | | 31-0 | 23-32-32 | D02491 | | 4 | | | | D02331 | | 2 | | 280-299 |
| 003 | 22 | PA | | 25-0 | 23-32-32 | D02491 | | 2 | | | | D02331 | | 10 | | 275-278 |
| 003 | 22 | PA | | 31-0 | 23-32-32 | D02491 | | 2 | | | | D02331 | | 10 | | 280-299 |
| 004 | 24 | PK | | 25-0 | 23-32-32 | D02491 | | 8 | | | | D02331 | | 6 | | 275-278 |
| 004 | 24 | PK | | 31-0 | 23-32-32 | D02491 | | 8 | | | | D02331 | | 6 | | 280-299 |
| 005 | 22 | PA | | 25-0 | 23-32-32 | SM00001 | | | | S | | D02331 | | 9 | | 275-278 |
| 005 | 22 | PA | | 31-0 | 23-32-32 | SM00001 | | | | S | | D02331 | | 9 | | 280-299 |
| 006 | 22 | PA | | 2-0 | 23-32-32 | D02491 | | 3 | | | | SM00001 | | S | | 275-278 |
| 006 | 22 | PA | | 1-0 | 23-32-32 | D02491 | | 3 | | | | SM00001 | | S | | 280-299 |
| 007 | 22 | PA | | 2-0 | 23-32-32 | D02491 | | 5 | | | | SM00001 | | S | | 275-278 |
| 007 | 22 | PA | | 1-0 | 23-32-32 | D02491 | | 5 | | | | SM00001 | | S | | 280-299 |
| 008 | 22 | PA | | 2-0 | 23-32-32 | D02491 | | 6 | | | | SM00001 | | S | | 275-278 |
| 008 | 22 | PA | | 1-0 | 23-32-32 | D02491 | | 6 | | | | SM00001 | | S | | 280-299 |
| 009 | 22 | PA | | 2-0 | 23-32-32 | D02491 | | 7 | | | | SM00001 | | S | | 275-278 |
| 009 | 22 | PA | | 1-0 | 23-32-32 | D02491 | | 7 | | | | SM00001 | | S | | 280-299 |
| 01CO | | | A | 0-0 | 23-32-32 | D02489 | | = C1 | | | | D02331 | | = C1 | | 275-278 |
| 01CO | | | A | 0-0 | 23-32-32 | D02491 | | = C1 | | | | D02331 | | = C1 | | 280-299 |
| 01CX | | 5X | A | 25-0 | 23-32-32 | D02489 | | = A1 | | | | D02331 | | = A1 | | 275-278 |
| 01CX | | 5X | A | 31-0 | 23-32-32 | D02491 | | = A1 | | | | D02331 | | = A1 | | 280-299 |
| W1809 | 286T1809 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | |
| 001 | 20 | PA | | 41-0 | 23-32-33 | D02103 | | 1 | | | | D02339 | | 1 | | 275-299 |
| 002 | 20 | PA | | 41-0 | 23-32-33 | D02103 | | 4 | | | | D02339 | | 2 | | 275-299 |
| 003 | 22 | PA | | 41-0 | 23-32-33 | D02103 | | 2 | | | | D02339 | | 10 | | 275-299 |
| 004 | 24 | PK | | 41-0 | 23-32-33 | D02103 | | 8 | | | | D02339 | | 6 | | 275-299 |
| 005 | 22 | PA | | 41-0 | 23-32-33 | SM00001 | | | | S | | D02339 | | 9 | | 275-299 |
| 006 | 22 | PA | | 2-0 | 23-32-33 | D02103 | | 3 | | | | SM00001 | | S | | 275-299 |
| 007 | 22 | PA | | 2-0 | 23-32-33 | D02103 | | 5 | | | | SM00001 | | S | | 275-299 |
| 008 | 22 | PA | | 2-0 | 23-32-33 | D02103 | | 6 | | | | SM00001 | | S | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1800

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|---|-------|----------|-------------|------|------|-----------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1809 | 286T1809 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR (continued) | | | | | | | | | | | |
| 009 | 22 | | PA | | 2-0 | 23-32-33 | D02103 | | 7 | | SM00001 | | S | | 275-299 |
| 01CO | | | | A | 0-0 | 23-32-33 | D02103 | | = C1 | | D02339 | | = C1 | | 275-299 |
| 01CX | | 5X | | A | 41-0 | 23-32-33 | D02103 | | = A1 | | D02339 | | = A1 | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1800
Page 3 End
Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1811 | 286T1811 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | |
| 001 | 20 | | PA | 25-0 | 23-32-33 | D02107 | | 1 | | | | D02341 | | 1 | | 275-299 |
| 002 | 20 | | PA | 25-0 | 23-32-33 | D02107 | | 4 | | | | D02341 | | 2 | | 275-299 |
| 003 | 22 | | PA | 25-0 | 23-32-33 | D02107 | | 2 | | | | D02341 | | 10 | | 275-299 |
| 004 | 24 | | PK | 25-0 | 23-32-33 | D02107 | | 8 | | | | D02341 | | 6 | | 275-299 |
| 005 | 22 | | PA | 25-0 | 23-32-33 | SM00001 | | | | S | | D02341 | | 9 | | 275-299 |
| 006 | 22 | | PA | 2-0 | 23-32-33 | D02107 | | 3 | | | | SM00001 | | | S | 275-299 |
| 007 | 22 | | PA | 2-0 | 23-32-33 | D02107 | | 5 | | | | SM00001 | | | S | 275-299 |
| 008 | 22 | | PA | 2-0 | 23-32-33 | D02107 | | 6 | | | | SM00001 | | | S | 275-299 |
| 009 | 22 | | PA | 2-0 | 23-32-33 | D02107 | | 7 | | | | SM00001 | | | S | 275-299 |
| 01CO | | | A | 0-0 | 23-32-33 | D02107 | | | | = C1 | | D02341 | | = C1 | | 275-299 |
| 01CX | | 5X | A | 25-0 | 23-32-33 | D02107 | | | | = A1 | | D02341 | | = A1 | | 275-299 |
| W1813 | 286T1813 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | |
| 001 | 20 | | PA | 41-0 | 23-32-34 | D02165 | | 1 | | | | D02347 | | 1 | | 275-278 |
| 001 | 20 | | PA | 33-0 | 23-32-34 | D02165 | | 1 | | | | D02347 | | 1 | | 280-299 |
| 002 | 20 | | PA | 41-0 | 23-32-34 | D02165 | | 4 | | | | D02347 | | 2 | | 275-278 |
| 002 | 20 | | PA | 33-0 | 23-32-34 | D02165 | | 4 | | | | D02347 | | 2 | | 280-299 |
| 003 | 22 | | PA | 41-0 | 23-32-34 | D02165 | | 2 | | | | D02347 | | 10 | | 275-278 |
| 003 | 22 | | PA | 33-0 | 23-32-34 | D02165 | | 2 | | | | D02347 | | 10 | | 280-299 |
| 004 | 24 | | PK | 41-0 | 23-32-34 | D02165 | | 8 | | | | D02347 | | 6 | | 275-278 |
| 004 | 24 | | PK | 33-0 | 23-32-34 | D02165 | | 8 | | | | D02347 | | 6 | | 280-299 |
| 005 | 22 | | PA | 41-0 | 23-32-34 | SM00001 | | | | S | | D02347 | | 9 | | 275-278 |
| 005 | 22 | | PA | 33-0 | 23-32-34 | SM00001 | | | | S | | D02347 | | 9 | | 280-299 |
| 006 | 22 | | PA | 2-0 | 23-32-34 | D02165 | | 3 | | | | SM00001 | | | S | 275-278 |
| 006 | 22 | | PA | 1-0 | 23-32-34 | D02165 | | 3 | | | | SM00001 | | | S | 280-299 |
| 007 | 22 | | PA | 2-0 | 23-32-34 | D02165 | | 5 | | | | SM00001 | | | S | 275-278 |
| 007 | 22 | | PA | 1-0 | 23-32-34 | D02165 | | 5 | | | | SM00001 | | | S | 280-299 |
| 008 | 22 | | PA | 2-0 | 23-32-34 | D02165 | | 6 | | | | SM00001 | | | S | 275-278 |
| 008 | 22 | | PA | 1-0 | 23-32-34 | D02165 | | 6 | | | | SM00001 | | | S | 280-299 |
| 009 | 22 | | PA | 2-0 | 23-32-34 | D02165 | | 7 | | | | SM00001 | | | S | 275-278 |
| 009 | 22 | | PA | 1-0 | 23-32-34 | D02165 | | 7 | | | | SM00001 | | | S | 280-299 |
| 01CO | | | A | 0-0 | 23-32-34 | D02177 | | | | = C1 | | D02347 | | = C1 | | 275-278 |
| 01CO | | | A | 0-0 | 23-32-34 | D02165 | | | | = C1 | | D02347 | | = C1 | | 280-299 |
| 01CX | | 5X | A | 41-0 | 23-32-34 | D02177 | | | | = A1 | | D02347 | | = A1 | | 275-278 |
| 01CX | | 5X | A | 33-0 | 23-32-34 | D02165 | | | | = A1 | | D02347 | | = A1 | | 280-299 |
| W1815 | 286T1815 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | |
| 001 | 20 | | PA | 22-0 | 23-32-34 | D02163 | | 1 | | | | D02349 | | 1 | | 275-276 |
| 001 | 20 | | PA | 33-0 | 23-32-34 | D02163 | | 1 | | | | D02349 | | 1 | | 277-278 |

WIRE LIST

D280T132

91-21-11

Section W1810

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1815 | 286T1815 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR (continued) | | | | | | | | | | | |
| 001 | 20 | | PA | | 29-0 | 23-32-34 | D02163 | | | | D02349 | | | | 280-299 |
| 002 | 20 | | PA | | 22-0 | 23-32-34 | D02163 | | | | D02349 | | | | 275-276 |
| 002 | 20 | | PA | | 33-0 | 23-32-34 | D02163 | | | | D02349 | | | | 277-278 |
| 002 | 20 | | PA | | 29-0 | 23-32-34 | D02163 | | | | D02349 | | | | 280-299 |
| 003 | 22 | | PA | | 22-0 | 23-32-34 | D02163 | | | | D02349 | | 10 | | 275-276 |
| 003 | 22 | | PA | | 33-0 | 23-32-34 | D02163 | | | | D02349 | | 10 | | 277-278 |
| 003 | 22 | | PA | | 29-0 | 23-32-34 | D02163 | | | | D02349 | | 10 | | 280-299 |
| 004 | 24 | | PK | | 22-0 | 23-32-34 | D02163 | | | | D02349 | | | 6 | 275-276 |
| 004 | 24 | | PK | | 33-0 | 23-32-34 | D02163 | | | | D02349 | | | 6 | 277-278 |
| 004 | 24 | | PK | | 29-0 | 23-32-34 | D02163 | | | | D02349 | | | 6 | 280-299 |
| 005 | 22 | | PA | | 22-0 | 23-32-34 | SM00001 | | | | D02349 | | | 9 | 275-276 |
| 005 | 22 | | PA | | 33-0 | 23-32-34 | SM00001 | | | | D02349 | | | 9 | 277-278 |
| 005 | 22 | | PA | | 29-0 | 23-32-34 | SM00001 | | | | D02349 | | | 9 | 280-299 |
| 006 | 22 | | PA | | 2-0 | 23-32-34 | D02163 | | | 3 | SM00001 | | | S | 275-278 |
| 006 | 22 | | PA | | 1-0 | 23-32-34 | D02163 | | | 3 | SM00001 | | | S | 280-299 |
| 007 | 22 | | PA | | 2-0 | 23-32-34 | D02163 | | | 5 | SM00001 | | | S | 275-278 |
| 007 | 22 | | PA | | 1-0 | 23-32-34 | D02163 | | | 5 | SM00001 | | | S | 280-299 |
| 008 | 22 | | PA | | 2-0 | 23-32-34 | D02163 | | | 6 | SM00001 | | | S | 275-278 |
| 008 | 22 | | PA | | 1-0 | 23-32-34 | D02163 | | | 6 | SM00001 | | | S | 280-299 |
| 009 | 22 | | PA | | 2-0 | 23-32-34 | D02163 | | | 7 | SM00001 | | | S | 275-278 |
| 009 | 22 | | PA | | 1-0 | 23-32-34 | D02163 | | | 7 | SM00001 | | | S | 280-299 |
| 01CO | | | | A | 0-0 | 23-32-34 | D02163 | | | =C1 | D02349 | | | =C1 | 275-299 |
| 01CX | | 5X | | A | 22-0 | 23-32-34 | D02163 | | | =A1 | D02349 | | | =A1 | 275-276 |
| 01CX | | 5X | | A | 33-0 | 23-32-34 | D02163 | | | =A1 | D02349 | | | =A1 | 277-278 |
| 01CX | | 5X | | A | 29-0 | 23-32-34 | D02163 | | | =A1 | D02349 | | | =A1 | 280-299 |
| W1817 | 286T1817 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 20 | | PA | | 39-0 | 23-32-41 | D02363 | | | | D02355 | | | | 275-278 |
| 001 | 20 | | PA | | 19-0 | 23-32-41 | D02363 | | | | D02355 | | | | 280-299 |
| 002 | 20 | | PA | | 39-0 | 23-32-41 | D02363 | | | | D02355 | | | | 275-278 |
| 002 | 20 | | PA | | 19-0 | 23-32-41 | D02363 | | | | D02355 | | | | 280-299 |
| 003 | 22 | | PA | | 39-0 | 23-32-41 | D02363 | | | | D02355 | | 10 | | 275-278 |
| 003 | 22 | | PA | | 19-0 | 23-32-41 | D02363 | | | | D02355 | | 10 | | 280-299 |
| 004 | 24 | | PK | | 39-0 | 23-32-41 | D02363 | | | | D02355 | | | 6 | 275-278 |
| 004 | 24 | | PK | | 19-0 | 23-32-41 | D02363 | | | | D02355 | | | 6 | 280-299 |
| 005 | 22 | | PA | | 39-0 | 23-32-41 | SM00001 | | | | D02355 | | | 9 | 275-278 |
| 005 | 22 | | PA | | 19-0 | 23-32-41 | SM00001 | | | | D02355 | | | 9 | 280-299 |
| 006 | 22 | | PA | | 2-0 | 23-32-41 | D02363 | | | 3 | SM00001 | | | S | 275-299 |
| 007 | 22 | | PA | | 2-0 | 23-32-41 | D02363 | | | 5 | SM00001 | | | S | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1810

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|-------|------|---------|--------|------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1817 | 286T1817 | | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR (continued) | | | | | | | | | | | | |
| 008 | 22 | | PA | | 2-0 | 23-32-41 | D02363 | | 6 | | | | SM00001 | | S | | 275-299 |
| 009 | 22 | | PA | | 2-0 | 23-32-41 | D02363 | | 7 | | | | SM00001 | | S | | 275-278 |
| 009 | 22 | | PA | | 1-0 | 23-32-41 | D02363 | | 7 | | | | SM00001 | | S | | 280-299 |
| 01CO | | | | A | 0-0 | 23-32-41 | D02493 | | = C1 | | | | D02355 | | = C1 | | 275-299 |
| 01CX | | 5X | | A | 39-0 | 23-32-41 | D02493 | | = A1 | | | | D02355 | | = A1 | | 275-278 |
| 01CX | | 5X | | A | 19-0 | 23-32-41 | D02493 | | = A1 | | | | D02355 | | = A1 | | 280-299 |
| W1819 | 286T1819 | | | | VIDEO DIST UNIT #5 TO PROJECTOR/MONITOR -10 | | | | | | | | | | | | |
| 001 | 20 | | PA | | 29-0 | 23-32-41 | D02365 | | 1 | | | | D02357 | | 1 | | 275-278 |
| 001 | 20 | | PA | | 18-0 | 23-32-41 | D02365 | | 1 | | | | D02357 | | 1 | | 280-299 |
| 002 | 20 | | PA | | 29-0 | 23-32-41 | D02365 | | 4 | | | | D02357 | | 2 | | 275-278 |
| 002 | 20 | | PA | | 18-0 | 23-32-41 | D02365 | | 4 | | | | D02357 | | 2 | | 280-299 |
| 003 | 22 | | PA | | 29-0 | 23-32-41 | D02365 | | 2 | | | | D02357 | | 10 | | 275-278 |
| 003 | 22 | | PA | | 18-0 | 23-32-41 | D02365 | | 2 | | | | D02357 | | 10 | | 280-299 |
| 004 | 24 | | PK | | 29-0 | 23-32-41 | D02365 | | 8 | | | | D02357 | | 6 | | 275-278 |
| 004 | 24 | | PK | | 18-0 | 23-32-41 | D02365 | | 8 | | | | D02357 | | 6 | | 280-299 |
| 005 | 22 | | PA | | 29-0 | 23-32-41 | SM00001 | | | S | | | D02357 | | 9 | | 275-278 |
| 005 | 22 | | PA | | 18-0 | 23-32-41 | SM00001 | | | S | | | D02357 | | 9 | | 280-299 |
| 006 | 22 | | PA | | 2-0 | 23-32-41 | D02365 | | 3 | | | | SM00001 | | S | | 275-278 |
| 006 | 22 | | PA | | 1-0 | 23-32-41 | D02365 | | 3 | | | | SM00001 | | S | | 280-299 |
| 007 | 22 | | PA | | 2-0 | 23-32-41 | D02365 | | 5 | | | | SM00001 | | S | | 275-278 |
| 007 | 22 | | PA | | 1-0 | 23-32-41 | D02365 | | 5 | | | | SM00001 | | S | | 280-299 |
| 008 | 22 | | PA | | 2-0 | 23-32-41 | D02365 | | 6 | | | | SM00001 | | S | | 275-278 |
| 008 | 22 | | PA | | 1-0 | 23-32-41 | D02365 | | 6 | | | | SM00001 | | S | | 280-299 |
| 009 | 22 | | PA | | 2-0 | 23-32-41 | D02365 | | 7 | | | | SM00001 | | S | | 275-278 |
| 009 | 22 | | PA | | 1-0 | 23-32-41 | D02365 | | 7 | | | | SM00001 | | S | | 280-299 |
| 01CO | | | | A | 0-0 | 23-32-41 | D02495 | | = C1 | | | | D02357 | | = C1 | | 275-299 |
| 01CX | | 5X | | A | 29-0 | 23-32-41 | D02495 | | = A1 | | | | D02357 | | = A1 | | 275-278 |
| 01CX | | 5X | | A | 18-0 | 23-32-41 | D02495 | | = A1 | | | | D02357 | | = A1 | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1810

Page 3 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|---|-------|------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1821 | 286T1821 | VIDEO DIST UNIT #6 TO PROJECTOR/MONITOR -11 | | | | | | | | | | | | | |
| 001 | 20 | PA | | 36-0 | 23-32-42 | D02375 | | 1 | | | D02367 | | 1 | | 275-278 |
| 001 | 20 | PA | | 25-0 | 23-32-42 | D02375 | | 1 | | | D02367 | | 1 | | 280-299 |
| 002 | 20 | PA | | 36-0 | 23-32-42 | D02375 | | 4 | | | D02367 | | 2 | | 275-278 |
| 002 | 20 | PA | | 25-0 | 23-32-42 | D02375 | | 4 | | | D02367 | | 2 | | 280-299 |
| 003 | 22 | PA | | 36-0 | 23-32-42 | D02375 | | 2 | | | D02367 | | 10 | | 275-278 |
| 003 | 22 | PA | | 25-0 | 23-32-42 | D02375 | | 2 | | | D02367 | | 10 | | 280-299 |
| 004 | 24 | PK | | 36-0 | 23-32-42 | D02375 | | 8 | | | D02367 | | 6 | | 275-278 |
| 004 | 24 | PK | | 25-0 | 23-32-42 | D02375 | | 8 | | | D02367 | | 6 | | 280-299 |
| 005 | 22 | PA | | 36-0 | 23-32-42 | SM00001 | | | S | | D02367 | | 9 | | 275-278 |
| 005 | 22 | PA | | 25-0 | 23-32-42 | SM00001 | | | S | | D02367 | | 9 | | 280-299 |
| 006 | 22 | PA | | 2-0 | 23-32-42 | D02375 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | PA | | 2-0 | 23-32-42 | D02375 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | PA | | 2-0 | 23-32-42 | D02375 | | 6 | | | SM00001 | | | S | 275-299 |
| 009 | 22 | PA | | 2-0 | 23-32-42 | D02375 | | 7 | | | SM00001 | | | S | 275-299 |
| 01CO | | | A | 0-0 | 23-32-42 | D02375 | | = C1 | | | D02367 | | = C1 | | 275-299 |
| 01CX | | 5X | A | 36-0 | 23-32-42 | D02375 | | = A1 | | | D02367 | | = A1 | | 275-278 |
| 01CX | | 5X | A | 25-0 | 23-32-42 | D02375 | | = A1 | | | D02367 | | = A1 | | 280-299 |
| W1823 | 286T1823 | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | | |
| 001 | 20 | PA | | 26-0 | 23-32-42 | D02369 | | 1 | | | D02513 | | 1 | | 275-278 |
| 001 | 20 | PA | | 22-0 | 23-32-42 | D02369 | | 1 | | | D02513 | | 1 | | 280-299 |
| 002 | 20 | PA | | 26-0 | 23-32-42 | D02369 | | 2 | | | D02513 | | 4 | | 275-278 |
| 002 | 20 | PA | | 22-0 | 23-32-42 | D02369 | | 2 | | | D02513 | | 4 | | 280-299 |
| 003 | 22 | PA | | 27-0 | 23-32-42 | D02369 | | 10 | | | D02513 | | 2 | | 275-278 |
| 003 | 22 | PA | | 22-0 | 23-32-42 | D02369 | | 10 | | | D02513 | | 2 | | 280-299 |
| 004 | 24 | PK | | 26-0 | 23-32-42 | D02369 | | 6 | | | D02513 | | 8 | | 275-278 |
| 004 | 24 | PK | | 22-0 | 23-32-42 | D02369 | | 6 | | | D02513 | | 8 | | 280-299 |
| 005 | 22 | PA | | 26-0 | 23-32-42 | SM00001 | | | S | | D02369 | | 9 | | 275-278 |
| 005 | 22 | PA | | 22-0 | 23-32-42 | SM00001 | | | S | | D02369 | | 9 | | 280-299 |
| 006 | 22 | PA | | 2-0 | 23-32-42 | D02513 | | 3 | | | SM00001 | | | S | 275-278 |
| 006 | 22 | PA | | 1-0 | 23-32-42 | D02513 | | 3 | | | SM00001 | | | S | 280-299 |
| 007 | 22 | PA | | 2-0 | 23-32-42 | D02513 | | 5 | | | SM00001 | | | S | 275-278 |
| 007 | 22 | PA | | 1-0 | 23-32-42 | D02513 | | 5 | | | SM00001 | | | S | 280-299 |
| 008 | 22 | PA | | 2-0 | 23-32-42 | D02513 | | 6 | | | SM00001 | | | S | 275-278 |
| 008 | 22 | PA | | 1-0 | 23-32-42 | D02513 | | 6 | | | SM00001 | | | S | 280-299 |
| 009 | 22 | PA | | 2-0 | 23-32-42 | D02513 | | 7 | | | SM00001 | | | S | 275-278 |
| 009 | 22 | PA | | 1-0 | 23-32-42 | D02513 | | 7 | | | SM00001 | | | S | 280-299 |
| 01CO | | | A | 0-0 | 23-32-42 | D02369 | | = C1 | | | D02513 | | = C1 | | 275-299 |
| 01CX | | 5X | A | 26-0 | 23-32-42 | D02369 | | = A1 | | | D02513 | | = A1 | | 275-278 |

WIRE LIST

D280T132

91-21-11

Section W1820

Page 1

Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1823 | 286T1823 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR (continued) | | | | | | | | | | | | |
| 01CX | | 5X | A | 22-0 | 23-32-42 | D02369 | = A1 | | | | D02513 | = A1 | | | 280-299 | |
| W1825 | 286T1825 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | |
| 001 | 20 | PA | | 50-0 | 23-32-43 | D02169 | | 1 | | | D02377 | | 1 | | 275-278 | |
| 001 | 20 | PA | | 42-0 | 23-32-43 | D02169 | | 1 | | | D02377 | | 1 | | 280-299 | |
| 002 | 20 | PA | | 50-0 | 23-32-43 | D02169 | | 4 | | | D02377 | | 2 | | 275-278 | |
| 002 | 20 | PA | | 42-0 | 23-32-43 | D02169 | | 4 | | | D02377 | | 2 | | 280-299 | |
| 003 | 22 | PA | | 50-0 | 23-32-43 | D02169 | | 2 | | | D02377 | | 10 | | 275-278 | |
| 003 | 22 | PA | | 42-0 | 23-32-43 | D02169 | | 2 | | | D02377 | | 10 | | 280-299 | |
| 004 | 24 | PK | | 50-0 | 23-32-43 | D02169 | | 8 | | | D02377 | | 6 | | 275-278 | |
| 004 | 24 | PK | | 42-0 | 23-32-43 | D02169 | | 8 | | | D02377 | | 6 | | 280-299 | |
| 005 | 22 | PA | | 50-0 | 23-32-43 | SM00001 | | | S | | D02377 | | 9 | | 275-278 | |
| 005 | 22 | PA | | 42-0 | 23-32-43 | SM00001 | | | S | | D02377 | | 9 | | 280-299 | |
| 006 | 22 | PA | | 2-0 | 23-32-43 | D02169 | | 3 | | | SM00001 | | | S | 275-278 | |
| 006 | 22 | PA | | 1-0 | 23-32-43 | D02169 | | 3 | | | SM00001 | | | S | 280-299 | |
| 007 | 22 | PA | | 2-0 | 23-32-43 | D02169 | | 5 | | | SM00001 | | | S | 275-278 | |
| 007 | 22 | PA | | 1-0 | 23-32-43 | D02169 | | 5 | | | SM00001 | | | S | 280-299 | |
| 008 | 22 | PA | | 2-0 | 23-32-43 | D02169 | | 6 | | | SM00001 | | | S | 275-278 | |
| 008 | 22 | PA | | 1-0 | 23-32-43 | D02169 | | 6 | | | SM00001 | | | S | 280-299 | |
| 009 | 22 | PA | | 2-0 | 23-32-43 | D02169 | | 7 | | | SM00001 | | | S | 275-278 | |
| 009 | 22 | PA | | 1-0 | 23-32-43 | D02169 | | 7 | | | SM00001 | | | S | 280-299 | |
| 01CO | | | A | 0-0 | 23-32-43 | D02169 | | | = C1 | | D02377 | | | = C1 | 275-278 | |
| 01CO | | | A | 0-0 | 23-32-43 | D02181 | | | = C1 | | D02377 | | | = C1 | 280-299 | |
| 01CX | | 5X | A | 50-0 | 23-32-43 | D02169 | | | = A1 | | D02377 | | | = A1 | 275-278 | |
| 01CX | | 5X | A | 42-0 | 23-32-43 | D02181 | | | = A1 | | D02377 | | | = A1 | 280-299 | |

WIRE LIST

D280T132

91-21-11

Section W1820

Page 2 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1833 | 286T1833 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 20 | | PA | 46-0 | 23-32-51 | D02393 | | 1 | | | D02385 | | 1 | | 275-299 |
| 002 | 20 | | PA | 46-0 | 23-32-51 | D02393 | | 4 | | | D02385 | | 2 | | 275-299 |
| 003 | 22 | | PA | 46-0 | 23-32-51 | D02393 | | 2 | | | D02385 | | 10 | | 275-299 |
| 004 | 24 | | PK | 46-0 | 23-32-51 | D02393 | | 8 | | | D02385 | | 6 | | 275-299 |
| 005 | 22 | | PA | 46-0 | 23-32-51 | SM00001 | | | S | | D02385 | | 9 | | 275-299 |
| 006 | 22 | | PA | 2-0 | 23-32-51 | D02393 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | | PA | 2-0 | 23-32-51 | D02393 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | | PA | 2-0 | 23-32-51 | D02393 | | 6 | | | SM00001 | | | S | 275-299 |
| 009 | 22 | | PA | 2-0 | 23-32-51 | D02393 | | 7 | | | SM00001 | | | S | 275-299 |
| 01CO | | | A | 0-0 | 23-32-51 | D02395 | | | =C1 | | D02385 | | =C1 | | 275-299 |
| 01CX | | 5X | A | 46-0 | 23-32-51 | D02395 | | | =A1 | | D02385 | | =A1 | | 275-299 |
| W1835 | 286T1835 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 20 | | PA | 36-0 | 23-32-51 | D02397 | | 1 | | | D02387 | | 1 | | 275-299 |
| 002 | 20 | | PA | 36-0 | 23-32-51 | D02397 | | 4 | | | D02387 | | 2 | | 275-299 |
| 003 | 22 | | PA | 36-0 | 23-32-51 | D02397 | | 2 | | | D02387 | | 10 | | 275-299 |
| 004 | 24 | | PK | 36-0 | 23-32-51 | D02397 | | 8 | | | D02387 | | 6 | | 275-299 |
| 005 | 22 | | PA | 36-0 | 23-32-51 | SM00001 | | | S | | D02387 | | 9 | | 275-299 |
| 006 | 22 | | PA | 2-0 | 23-32-51 | D02397 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | | PA | 2-0 | 23-32-51 | D02397 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | | PA | 2-0 | 23-32-51 | D02397 | | 6 | | | SM00001 | | | S | 275-299 |
| 009 | 22 | | PA | 2-0 | 23-32-51 | D02397 | | 7 | | | SM00001 | | | S | 275-299 |
| 01CO | | | A | 0-0 | 23-32-51 | D02399 | | | =C1 | | D02387 | | =C1 | | 275-299 |
| 01CX | | 5X | A | 36-0 | 23-32-51 | D02399 | | | =A1 | | D02387 | | =A1 | | 275-299 |
| W1837 | 286T1837 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 20 | | PA | 46-9 | 23-32-52 | D02073 | | 1 | | | D02401 | | 1 | | 275-299 |
| 002 | 20 | | PA | 46-9 | 23-32-52 | D02073 | | 4 | | | D02401 | | 2 | | 275-299 |
| 003 | 22 | | PA | 46-9 | 23-32-52 | D02073 | | 2 | | | D02401 | | 10 | | 275-299 |
| 004 | 24 | | PK | 46-9 | 23-32-52 | D02073 | | 8 | | | D02401 | | 6 | | 275-299 |
| 005 | 22 | | PA | 46-0 | 23-32-52 | SM00001 | | | S | | D02401 | | 9 | | 275-299 |
| 006 | 22 | | PA | 2-0 | 23-32-52 | D02073 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | | PA | 2-0 | 23-32-52 | D02073 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | | PA | 2-0 | 23-32-52 | D02073 | | 6 | | | SM00001 | | | S | 275-299 |
| 009 | 22 | | PA | 2-0 | 23-32-52 | D02073 | | 7 | | | SM00001 | | | S | 275-299 |
| 01CO | | | A | 0-0 | 23-32-52 | D02077 | | | =C1 | | D02401 | | =C1 | | 275-299 |
| 01CX | | 5X | A | 46-9 | 23-32-52 | D02077 | | | =A1 | | D02401 | | =A1 | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W1830

Page 1

Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1839 | 286T1839 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | |
| 001 | 20 | | PA | | 21-0 | 23-32-52 | D02071 | | 1 | | | D02403 | | 1 | | 275-299 |
| 002 | 20 | | PA | | 21-0 | 23-32-52 | D02071 | | 4 | | | D02403 | | 2 | | 275-299 |
| 003 | 22 | | PA | | 21-0 | 23-32-52 | D02071 | | 2 | | | D02403 | | 10 | | 275-299 |
| 004 | 24 | | PK | | 21-0 | 23-32-52 | D02071 | | 8 | | | D02403 | | 6 | | 275-299 |
| 005 | 22 | | PA | | 21-0 | 23-32-52 | SM00001 | | | S | | D02403 | | 9 | | 275-299 |
| 006 | 22 | | PA | | 2-0 | 23-32-52 | D02071 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | | PA | | 2-0 | 23-32-52 | D02071 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | | PA | | 2-0 | 23-32-52 | D02071 | | 6 | | | SM00001 | | | S | 275-299 |
| 009 | 22 | | PA | | 2-0 | 23-32-52 | D02071 | | 7 | | | SM00001 | | | S | 275-299 |
| 01CO | | | | A | 0-0 | 23-32-52 | D02075 | | | = C1 | | D02403 | | = C1 | | 275-299 |
| 01CX | | | | A | 21-0 | 23-32-52 | D02075 | | | = A1 | | D02403 | | = A1 | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1830
Page 2 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1841 | 286T1841 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 20 | | PA | 39-0 | 23-32-53 | D02417 | | 1 | | | D02409 | | 1 | | 275-299 |
| 002 | 20 | | PA | 39-0 | 23-32-53 | D02417 | | 4 | | | D02409 | | 2 | | 275-299 |
| 003 | 22 | | PA | 39-0 | 23-32-53 | D02417 | | 2 | | | D02409 | | 10 | | 275-299 |
| 004 | 24 | | PK | 39-0 | 23-32-53 | D02417 | | 8 | | | D02409 | | 6 | | 275-299 |
| 005 | 22 | | PA | 39-0 | 23-32-53 | SM00001 | | | S | | D02409 | | 9 | | 275-299 |
| 006 | 22 | | PA | 2-0 | 23-32-53 | D02417 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | | PA | 2-0 | 23-32-53 | D02417 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | | PA | 2-0 | 23-32-53 | D02417 | | 6 | | | SM00001 | | | S | 275-299 |
| 009 | 22 | | PA | 2-0 | 23-32-53 | D02417 | | 7 | | | SM00001 | | | S | 275-299 |
| 01CO | | | A | 0-0 | 23-32-53 | D02497 | | | = C1 | | D02409 | | = C1 | | 275-299 |
| 01CX | | 5X | A | 39-0 | 23-32-53 | D02497 | | | = A1 | | D02409 | | = A1 | | 275-299 |
| W1843 | 286T1843 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 20 | | PA | 29-0 | 23-32-53 | D02501 | | 1 | | | D02411 | | 1 | | 275-299 |
| 002 | 20 | | PA | 29-0 | 23-32-53 | D02501 | | 4 | | | D02411 | | 2 | | 275-299 |
| 003 | 22 | | PA | 29-0 | 23-32-53 | D02501 | | 2 | | | D02411 | | 10 | | 275-299 |
| 004 | 24 | | PK | 29-0 | 23-32-53 | D02501 | | 8 | | | D02411 | | 6 | | 275-299 |
| 005 | 22 | | PA | 29-0 | 23-32-53 | SM00001 | | | S | | D02411 | | 9 | | 275-299 |
| 006 | 22 | | PA | 2-0 | 23-32-53 | D02501 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | | PA | 2-0 | 23-32-53 | D02501 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | | PA | 2-0 | 23-32-53 | D02501 | | 6 | | | SM00001 | | | S | 275-299 |
| 009 | 22 | | PA | 2-0 | 23-32-53 | D02501 | | 7 | | | SM00001 | | | S | 275-299 |
| 01CO | | | A | 0-0 | 23-32-53 | D02499 | | | = C1 | | D02411 | | = C1 | | 275-299 |
| 01CX | | 5X | A | 29-0 | 23-32-53 | D02499 | | | = A1 | | D02411 | | = A1 | | 275-299 |
| W1845 | 286T1845 | | | VIDEO SPLITTER/VDU TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 20 | | PA | 42-0 | 23-32-54 | D01943 | | 1 | | | D02419 | | 1 | | 280-299 |
| 002 | 20 | | PA | 42-0 | 23-32-54 | D01943 | | 4 | | | D02419 | | 2 | | 280-299 |
| 003 | 22 | | PA | 42-0 | 23-32-54 | D01943 | | 2 | | | D02419 | | 10 | | 280-299 |
| 004 | 24 | | PK | 42-0 | 23-32-54 | D01943 | | 8 | | | D02419 | | 6 | | 280-299 |
| 005 | 22 | | PA | 42-0 | 23-32-54 | SM00001 | | | S | | D02419 | | 9 | | 280-299 |
| 006 | 22 | | PA | 1-0 | 23-32-54 | D01943 | | 3 | | | SM00001 | | | S | 280-299 |
| 007 | 22 | | PA | 1-0 | 23-32-54 | D01943 | | 5 | | | SM00001 | | | S | 280-299 |
| 008 | 22 | | PA | 1-0 | 23-32-54 | D01943 | | 6 | | | SM00001 | | | S | 280-299 |
| 009 | 22 | | PA | 1-0 | 23-32-54 | D01943 | | 7 | | | SM00001 | | | S | 280-299 |
| 01CO | | | A | 0-0 | 23-32-54 | D01943 | | | = C1 | | D02419 | | = C1 | | 280-299 |
| 01CX | | 5X | A | 42-0 | 23-32-54 | D01943 | | | = A1 | | D02419 | | = A1 | | 280-299 |

WIRE LIST

D280T132

91-21-11

Section W1840

Page 1

Mar 09/2006



| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|--------|-------|------|------|---------|-------------|------|-----------|
| | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | | |
| W1849 | 286T1849 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 20 | | PA | | 41-0 | 23-32-61 | D02435 | | 1 | | | D02427 | | 1 | 275-299 |
| 002 | 20 | | PA | | 41-0 | 23-32-61 | D02435 | | 4 | | | D02427 | | 2 | 275-299 |
| 003 | 22 | | PA | | 41-0 | 23-32-61 | D02435 | | 2 | | | D02427 | | 10 | 275-299 |
| 004 | 24 | | PK | | 41-0 | 23-32-61 | D02435 | | 8 | | | D02427 | | 6 | 275-299 |
| 005 | 22 | | PA | | 41-0 | 23-32-61 | SM00001 | | | S | | D02427 | | 9 | 275-299 |
| 006 | 22 | | PA | | 2-0 | 23-32-61 | D02435 | | 3 | | | SM00001 | | | S 275-299 |
| 007 | 22 | | PA | | 2-0 | 23-32-61 | D02435 | | 5 | | | SM00001 | | | S 275-299 |
| 008 | 22 | | PA | | 2-0 | 23-32-61 | D02435 | | 6 | | | SM00001 | | | S 275-299 |
| 009 | 22 | | PA | | 2-0 | 23-32-61 | D02435 | | 7 | | | SM00001 | | | S 275-299 |
| 01CO | | | | A | 0-0 | 23-32-61 | D02437 | | | = C1 | | D02427 | | = C1 | 275-299 |
| 01CX | | 5X | | A | 41-0 | 23-32-61 | D02437 | | | = A1 | | D02427 | | = A1 | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1840
Page 2 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1851 | 286T1851 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 20 | | PA | 32-0 | 23-32-61 | D02439 | | 1 | | | D02429 | | 1 | | 275-299 |
| 002 | 20 | | PA | 32-0 | 23-32-61 | D02439 | | 4 | | | D02429 | | 2 | | 275-299 |
| 003 | 22 | | PA | 32-0 | 23-32-61 | D02439 | | 2 | | | D02429 | | 10 | | 275-299 |
| 004 | 24 | | PK | 32-0 | 23-32-61 | D02439 | | 8 | | | D02429 | | 6 | | 275-299 |
| 005 | 22 | | PA | 32-0 | 23-32-61 | SM00001 | | | S | | D02429 | | 9 | | 275-299 |
| 006 | 22 | | PA | 2-0 | 23-32-61 | D02439 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | | PA | 2-0 | 23-32-61 | D02439 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | | PA | 2-0 | 23-32-61 | D02439 | | 6 | | | SM00001 | | | S | 275-299 |
| 009 | 22 | | PA | 2-0 | 23-32-61 | D02439 | | 7 | | | SM00001 | | | S | 275-299 |
| 01CO | | | A | 0-0 | 23-32-61 | D02441 | | | =C1 | | D02429 | | =C1 | | 275-299 |
| 01CX | | 5X | A | 32-0 | 23-32-61 | D02441 | | | =A1 | | D02429 | | =A1 | | 275-299 |
| W1853 | 286T1853 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 20 | | PA | 42-0 | 23-32-62 | D02173 | | 1 | | | D02443 | | 1 | | 275-299 |
| 002 | 20 | | PA | 42-0 | 23-32-62 | D02173 | | 4 | | | D02443 | | 2 | | 275-299 |
| 003 | 22 | | PA | 42-0 | 23-32-62 | D02173 | | 2 | | | D02443 | | 10 | | 275-299 |
| 004 | 24 | | PK | 42-0 | 23-32-62 | D02173 | | 8 | | | D02443 | | 6 | | 275-299 |
| 005 | 22 | | PA | 42-0 | 23-32-62 | SM00001 | | | S | | D02443 | | 9 | | 275-299 |
| 006 | 22 | | PA | 2-0 | 23-32-62 | D02173 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | | PA | 2-0 | 23-32-62 | D02173 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | | PA | 2-0 | 23-32-62 | D02173 | | 6 | | | SM00001 | | | S | 275-299 |
| 009 | 22 | | PA | 2-0 | 23-32-62 | D02173 | | 7 | | | SM00001 | | | S | 275-299 |
| 01CO | | | A | 0-0 | 23-32-62 | D02185 | | | =C1 | | D02443 | | =C1 | | 275-299 |
| 01CX | | 5X | A | 42-0 | 23-32-62 | D02185 | | | =A1 | | D02443 | | =A1 | | 275-299 |
| W1855 | 286T1855 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | |
| 001 | 20 | | PA | 17-0 | 23-32-62 | D02171 | | 1 | | | D02445 | | 1 | | 275-299 |
| 002 | 20 | | PA | 17-0 | 23-32-62 | D02171 | | 4 | | | D02445 | | 2 | | 275-299 |
| 003 | 22 | | PA | 17-0 | 23-32-62 | D02171 | | 2 | | | D02445 | | 10 | | 275-299 |
| 004 | 24 | | PK | 17-0 | 23-32-62 | D02171 | | 8 | | | D02445 | | 6 | | 275-299 |
| 005 | 22 | | PA | 17-0 | 23-32-62 | SM00001 | | | S | | D02445 | | 9 | | 275-299 |
| 006 | 22 | | PA | 2-0 | 23-32-62 | D02171 | | 3 | | | SM00001 | | | S | 275-299 |
| 007 | 22 | | PA | 2-0 | 23-32-62 | D02171 | | 5 | | | SM00001 | | | S | 275-299 |
| 008 | 22 | | PA | 2-0 | 23-32-62 | D02171 | | 6 | | | SM00001 | | | S | 275-299 |
| 009 | 22 | | PA | 2-0 | 23-32-62 | D02171 | | 7 | | | SM00001 | | | S | 275-299 |
| 01CO | | | A | 0-0 | 23-32-62 | D02183 | | | =C1 | | D02445 | | =C1 | | 275-299 |
| 01CX | | 5X | A | 17-0 | 23-32-62 | D02183 | | | =A1 | | D02445 | | =A1 | | 275-299 |

WIRE LIST
D280T132

91-21-11
Section W1850
Page 1
Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1857 | 286T1857 | | | VIDEO SPLITTER/VDU TO PROJECTOR/VIDEO MONTIOR CATIA DESIGNED | | | | | | | | | | | | |
| 001 | 20 | | PA | 24-0 | 23-32-44 | D02631 | | 1 | | | D02619 | | 1 | | 280-299 | |
| 002 | 20 | | PA | 24-0 | 23-32-44 | D02631 | | 4 | | | D02619 | | 2 | | 280-299 | |
| 003 | 22 | | PA | 24-0 | 23-32-44 | D02631 | | 2 | | | D02619 | | 10 | | 280-299 | |
| 004 | 24 | | PK | 24-0 | 23-32-44 | D02631 | | 8 | | | D02619 | | 6 | | 280-299 | |
| 005 | 22 | | PA | 24-0 | 23-32-44 | SM00001 | | | S | | D02619 | | 9 | | 280-299 | |
| 006 | 22 | | PA | 1-0 | 23-32-44 | D02631 | | 3 | | | SM00001 | | | S | 280-299 | |
| 007 | 22 | | PA | 1-0 | 23-32-44 | D02631 | | 5 | | | SM00001 | | | S | 280-299 | |
| 008 | 22 | | PA | 1-0 | 23-32-44 | D02631 | | 6 | | | SM00001 | | | S | 280-299 | |
| 009 | 22 | | PA | 1-0 | 23-32-44 | D02631 | | 7 | | | SM00001 | | | S | 280-299 | |
| 01CO | | | A | 0-0 | 23-32-44 | D02631 | | = C1 | | | D02619 | | = C1 | | 280-299 | |
| 01CX | | 5X | A | 24-0 | 23-32-44 | D02631 | | = A1 | | | D02619 | | = A1 | | 280-299 | |
| W1859 | 286T1859 | | | VIDEO SPLITTER/VDU TO PROJECTOR/VIDEO MONITOR CATIA DESIGNED | | | | | | | | | | | | |
| 001 | 20 | | PA | 31-0 | 23-32-44 | D02621 | | 1 | | | D02633 | | 1 | | 280-299 | |
| 002 | 20 | | PA | 31-0 | 23-32-44 | D02633 | | 4 | | | D02621 | | 2 | | 280-299 | |
| 003 | 22 | | PA | 31-0 | 23-32-44 | D02633 | | 2 | | | D02621 | | 10 | | 280-299 | |
| 004 | 24 | | PK | 31-0 | 23-32-44 | D02633 | | 8 | | | D02621 | | 6 | | 280-299 | |
| 005 | 22 | | PA | 31-0 | 23-32-44 | SM00001 | | | S | | D02621 | | 9 | | 280-299 | |
| 006 | 22 | | PA | 1-0 | 23-32-44 | D02633 | | 3 | | | SM00001 | | | S | 280-299 | |
| 007 | 22 | | PA | 1-0 | 23-32-44 | D02633 | | 5 | | | SM00001 | | | S | 280-299 | |
| 008 | 22 | | PA | 1-0 | 23-32-44 | D02633 | | 6 | | | SM00001 | | | S | 280-299 | |
| 009 | 22 | | PA | 1-0 | 23-32-44 | D02633 | | 7 | | | SM00001 | | | S | 280-299 | |
| 01CO | | | A | 0-0 | 23-32-44 | D02633 | | = C1 | | | D02621 | | = C1 | | 280-299 | |
| 01CX | | 5X | A | 31-0 | 23-32-44 | D02633 | | = A1 | | | D02621 | | = A1 | | 280-299 | |

WIRE LIST

D280T132

91-21-11

Section W1850

Page 2 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1865 | 286T1865 | | | VIDEO SPLITTER/VDU TO PROJECTOR/VIDEO MONITOR CATIA DESIGNED | | | | | | | | | | | |
| 001 | 20 | | PA | | 35-0 | 23-32-43 | D02167 | | | | D02379 | | | | 280-299 |
| 002 | 20 | | PA | | 35-0 | 23-32-43 | D02167 | | | | D02379 | | | | 280-299 |
| 003 | 22 | | PA | | 35-0 | 23-32-43 | D02167 | | | | D02379 | | 10 | | 280-299 |
| 004 | 24 | | PK | | 35-0 | 23-32-43 | D02167 | | | | D02379 | | 6 | | 280-299 |
| 005 | 22 | | PA | | 35-0 | 23-32-43 | SM00001 | | | | D02379 | | 9 | | 280-299 |
| 006 | 22 | | PA | | 2-0 | 23-32-43 | D02167 | | | | SM00001 | | | S | 280-299 |
| 007 | 22 | | PA | | 2-0 | 23-32-43 | D02167 | | | | SM00001 | | | S | 280-299 |
| 008 | 22 | | PA | | 2-0 | 23-32-43 | D02167 | | | | SM00001 | | | S | 280-299 |
| 009 | 22 | | PA | | 2-0 | 23-32-43 | D02167 | | | | SM00001 | | | S | 280-299 |
| 01CO | | | | A | 0-0 | 23-32-43 | D02179 | | | | D02379 | | | = C1 | 280-299 |
| 01CX | | | | A | 5X | 23-32-43 | D02179 | | | | D02379 | | | = A1 | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W1860
Page 1 End
Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1895 | 286T1895 | | | VIDEO SIGNAL SPLITTER TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | |
| 001 | 20 | PA | | 27-0 | 23-32-54 | D01941 | | 1 | | | D02421 | | 1 | | 280-299 | |
| 002 | 20 | PA | | 27-0 | 23-32-54 | D01941 | | 4 | | | D02421 | | 2 | | 280-299 | |
| 003 | 22 | PA | | 27-0 | 23-32-54 | D01941 | | 2 | | | D02421 | | 10 | | 280-299 | |
| 004 | 24 | PK | | 27-0 | 23-32-54 | D01941 | | 8 | | | D02421 | | 6 | | 280-299 | |
| 005 | 22 | PA | | 27-0 | 23-32-54 | SM00001 | | | S | | D02421 | | 9 | | 280-299 | |
| 006 | 22 | PA | | 2-0 | 23-32-54 | D01941 | | 3 | | | SM00001 | | | S | 280-299 | |
| 007 | 22 | PA | | 2-0 | 23-32-54 | D01941 | | 5 | | | SM00001 | | | S | 280-299 | |
| 008 | 22 | PA | | 2-0 | 23-32-54 | D01941 | | 6 | | | SM00001 | | | S | 280-299 | |
| 009 | 22 | PA | | 2-0 | 23-32-54 | D01941 | | 7 | | | SM00001 | | | S | 280-299 | |
| 01CO | | | A | 0-0 | 23-32-54 | D01941 | | = C1 | | | D02421 | | = C1 | | 280-299 | |
| 01CX | | 5X | A | 27-0 | 23-32-54 | D01941 | | = A1 | | | D02421 | | = A1 | | 280-299 | |
| W1897 | 286T1897 | | | VIDEO SPLITTER/VDU TO PROJECTOR/VIDEO MONITOR | | | | | | | | | | | | |
| 001 | 20 | PA | | 27-0 | 23-32-34 | D02917 | | 1 | | | D02915 | | 1 | | 280-299 | |
| 002 | 20 | PA | | 27-0 | 23-32-34 | D02917 | | 4 | | | D02915 | | 2 | | 280-299 | |
| 003 | 22 | PA | | 27-0 | 23-32-34 | D02917 | | 2 | | | D02915 | | 10 | | 280-299 | |
| 004 | 24 | PK | | 27-0 | 23-32-34 | D02917 | | 8 | | | D02915 | | 6 | | 280-299 | |
| 005 | 22 | PA | | 27-0 | 23-32-34 | SM00001 | | | S | | D02915 | | 9 | | 280-299 | |
| 006 | 22 | PA | | 1-0 | 23-32-34 | D02917 | | 3 | | | SM00001 | | | S | 280-299 | |
| 007 | 22 | PA | | 1-0 | 23-32-34 | D02917 | | 5 | | | SM00001 | | | S | 280-299 | |
| 008 | 22 | PA | | 1-0 | 23-32-34 | D02917 | | 6 | | | SM00001 | | | S | 280-299 | |
| 009 | 22 | PA | | 1-0 | 23-32-34 | D02917 | | 7 | | | SM00001 | | | S | 280-299 | |
| 01CO | | | A | 0-0 | 23-32-34 | D02913 | | = C1 | | | D02915 | | = C1 | | 280-299 | |
| 01CX | | 5X | A | 26-0 | 23-32-34 | D02913 | | = A1 | | | D02915 | | = A1 | | 280-299 | |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1901 | 286T1901 | | | | TCAS COAX-BOTTOM ANT. TO ANT. DISC. | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-45-11 | D02467 | = C1 | | | D06097P | = C1 | | | 050-099, 150-199, 277-299 | |
| 01CX | | | 78 | A | 1-1 | 34-45-11 | D02467 | = A1 | | | D06097P | = A1 | | | 050-099, 150-199, 277-299 | |
| 02CO | | | | B | 0-0 | 34-45-11 | D02613 | = C1 | | | D06127P | = C1 | | | 050-099, 150-199, 277-299 | |
| 02CX | | | 78 | B | 1-1 | 34-45-11 | D02613 | = A1 | | | D06127P | = A1 | | | 050-099, 150-199, 277-299 | |
| 03CO | | | | C | 0-0 | 34-45-11 | D02615 | = C1 | | | D06129P | = C1 | | | 050-099, 150-199, 277-299 | |
| 03CX | | | 78 | C | 1-1 | 34-45-11 | D02615 | = A1 | | | D06129P | = A1 | | | 050-099, 150-199, 277-299 | |
| 04CO | | | | D | 0-0 | 34-45-11 | D02617 | = C1 | | | D06131P | = C1 | | | 050-099, 150-199, 277-299 | |
| 04CX | | | 78 | D | 1-1 | 34-45-11 | D02617 | = A1 | | | D06131P | = A1 | | | 050-099, 150-199, 277-299 | |
| W1903 | 286T1903 | | | | E2-3 TO ATC RF SWITCH | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-53-13 | D04097J | = C1 | | | D02193 | = C1 | | | ALL | |
| 01CX | | | | JB | 4-0 | 34-53-13 | D04097J | = A1 | | | D02193 | = A1 | | | ALL | |
| W1905 | 286T1905 | | | | E2-2 TO ATC RF SWITCH | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-53-13 | D04093J | = C1 | | | D02189 | = C1 | | | ALL | |
| 01CX | | | | JB | 4-6 | 34-53-13 | D04093J | = A1 | | | D02189 | = A1 | | | ALL | |
| W1907 | 286T1907 | | | | E2-2 TO ATC RF SWITCH | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-53-13 | D04081J | = C1 | | | D02197 | = C1 | | | ALL | |
| 01CX | | | | JB | 5-4 | 34-53-13 | D04081J | = A1 | | | D02197 | = A1 | | | ALL | |
| W1909 | 286T1909 | | | | E2-3 TO ATC RF SWITCH | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 34-53-13 | D04085J | = C1 | | | D01441 | = C1 | | | ALL | |
| 01CX | | | | JB | 3-11 | 34-53-13 | D04085J | = A1 | | | D01441 | = A1 | | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W1900
Page 1 End
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1911 | 286T1911 | | | | COAX-SATCOM,M1791 LNA/DIP TO M1785 COMBINER | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-11 | D02661 | = | C1 | | D02681 | = | C1 | | | 156-157, 166-199, 277-299 |
| 01CX | | 78 | | A | 18-10 | 23-25-11 | D02661 | = | A1 | | D02681 | = | A1 | | | 156-157, 166-199, 277-299 |
| W1913 | 286T1913 | | | | COAX-SATCOM,M1784 SPLITTER TO E11 SHELF | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-11 | D02655 | = | C1 | | D06179P | = | C1 | | | 277-299 |
| 01CX | | 78 | | A | 13-0 | 23-25-11 | D02655 | = | A1 | | D06179P | = | A1 | | | 277-299 |
| W1915 | 286T1915 | | | | COAX-SATCOM,M1784 SPLITTER TO E9 | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-12 | D02659 | = | C1 | | D06175J | = | C1 | | | 277-299 |
| 01CX | | 78 | | A | 48-4 | 23-25-12 | D02659 | = | A1 | | D06175J | = | A1 | | | 277-299 |
| W1917 | 286T1917 | | | | COAX-SATCOM,M1784 SPLITTER TO E10 SHELF | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-12 | D06187P | = | C1 | | D02657 | = | C1 | | | 277-299 |
| 01CX | | 78 | | A | 15-12 | 23-25-12 | D06187P | = | A1 | | D02657 | = | A1 | | | 277-299 |
| W1919 | 286T1919 | | | | COAX-SATCOM,M1786 COMBINER TO E9 SHELF | | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-12 | D06177J | = | C1 | | D02665 | = | C1 | | | 277-299 |
| 01CX | | 78 | | A | 48-0 | 23-25-12 | D06177J | = | A1 | | D02665 | = | A1 | | | 277-299 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|-----|-------------|----------|---|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1921 | 286T1921 | | | | | | COAX-SATCOM,M1786 COMBINER TO M1790 LNA/DIP,RIGHT | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-17 | D02667 | = | C1 | | D02713 | = | C1 | | 277-299 | |
| 01CX | | 78 | | A | 12-0 | 23-25-17 | D02667 | = | A1 | | D02713 | = | A1 | | 277-299 | |
| W1923 | 286T1923 | | | | | | COAX-SATCOM,M1786 COMBINER TO M1789 LNA/DIP,LEFT | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-17 | D02705 | = | C1 | | D02669 | = | C1 | | 277-299 | |
| 01CX | | 78 | | A | 12-0 | 23-25-17 | D02705 | = | A1 | | D02669 | = | A1 | | 277-299 | |
| W1925 | 286T1925 | | | | | | COAX-SATCOM,M1785 COMBINER TO TOP HGA LNA/DIP | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-16 | D02663 | = | C1 | | D02767 | = | C1 | | 277-299 | |
| 01CX | | 78 | | A | 19-0 | 23-25-16 | D02663 | = | A1 | | D02767 | = | A1 | | 277-299 | |
| W1927 | 286T1927 | | | | | | COAX-SATCOM,M1788 LNA/DIP TO HGA, TOP TO E10 SHELF | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-16 | D02769 | = | C1 | | D06183P | = | C1 | | 277-299 | |
| 01CX | | | JB | A | 13-0 | 23-25-16 | D02769 | = | A1 | | D06183P | = | A1 | | 277-299 | |
| W1929 | 286T1929 | | | | | | COAX-SATCOM, M1787 HIGH PWR RLY TO M1789, LNA/DIP, L | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-17 | D02707 | = | C1 | | D02673 | = | C1 | | 156-157, 166-199, 277-299 | |
| 01CX | | | JB | A | 11-6 | 23-25-17 | D02707 | = | A1 | | D02673 | = | A1 | | 156-157, 166-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W1920
Page 1 End
Aug 15/2007



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1931 | 286T1931 | | | COAX-SATCOM,M1790 LNA/DIP,R TO M1787,HIGH PWR RLY | | | | | | | | | | | |
| 01CO | | | A | 0-0 | SPARE | D02675 | = | C1 | | D02715 | = | C1 | | 156-157, 166-199 | |
| 01CO | | | A | 0-0 | 23-25-17 | D02675 | = | C1 | | D02715 | = | C1 | | 277-299 | |
| 01CX | | JB | A | 12-0 | SPARE | D02675 | = | A1 | | D02715 | = | A1 | | 156-157, 166-199 | |
| 01CX | | JB | A | 12-0 | 23-25-17 | D02675 | = | A1 | | D02715 | = | A1 | | 277-299 | |
| W1933 | 286T1933 | | | COAX-SATCOM,M1787 HIGH PWR RLY TO E10 SHELF | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-17 | D02671 | = | C1 | | D06185P | = | C1 | | 277-299 | |
| 01CX | | JB | A | 18-0 | 23-25-17 | D02671 | = | A1 | | D06185P | = | A1 | | 277-299 | |
| W1935 | 286T1935 | | | COAX-SATCOM,M1791 LNA/DIP,LGA, TOP TO E11 SHELF | | | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-11 | D06181P | = | C1 | | D02683 | = | C1 | | 156-157, 166-199, 277-299 | |
| 01CX | | JB | A | 15-0 | 23-25-11 | D06181P | = | A1 | | D02683 | = | A1 | | 156-157, 166-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W1930
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 | | | | | | | | | | | | |
| AK01 | 24 | FA | A1 | 0-0 | 99-99-99 | D06240J | A01 | \$D | *1 | D00881A | REF | | | ALL | | |
| AK02 | 24 | FA | A1 | 0-0 | 73-31-11 | D06240J | A02 | \$D | *1 | D00881A | J08 | | | ALL | | |
| AK03 | 24 | FA | A1 | 0-0 | 73-31-11 | D06240J | A03 | \$D | *1 | D00881A | J09 | | | ALL | | |
| AK04 | 24 | FA | A1 | 0-0 | 73-31-11 | D06240J | A04 | \$D | *1 | D00881A | J07 | | | ALL | | |
| AK05 | 24 | FA | A1 | 0-0 | 79-32-11 | D06240J | A05 | \$D | *1 | D00881B | H02 | | | ALL | | |
| AK06 | 24 | FA | A1 | 0-0 | 79-32-11 | D06240J | A06 | \$D | *1 | GD00091 | A.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| AK06 | 24 | FA | A1 | 0-0 | 79-32-11 | D06240J | A06 | \$D | *1 | GDX0002 | A.. | 2 | | 155-157, 165-199, 277-299 | | |
| AK07 | 24 | FA | A1 | 0-0 | 79-32-11 | D06240J | A07 | \$D | *1 | D00881B | G01 | | | ALL | | |
| AK08 | 24 | FA | A1 | 0-0 | SPARE | D06240J | A08 | \$D | *1 | D00881A | REF | ** | | 050-099, 275-299 | | |
| AK08 | 24 | FA | A1 | 0-0 | SPARE | D06240J | A08 | \$D | *1 | D00881A | H11 | | | 150-199 | | |
| AK09 | 24 | FA | A1 | 0-0 | SPARE | D06240J | A09 | \$D | *1 | D00881A | REF | ** | | 050-099, 275-299 | | |
| AK09 | 24 | FA | A1 | 0-0 | SPARE | D06240J | A09 | \$D | *1 | D00881A | H10 | | | 150-199 | | |
| AK10 | 24 | FA | A1 | 0-0 | 79-32-11 | D06240J | A10 | \$D | *1 | TB0237X | A015 | BJ | | ALL | | |
| AK11 | 24 | FA | A1 | 0-0 | 73-34-11 | D06240J | A11 | \$D | *1 | D00881A | J11 | | | ALL | | |
| AK12 | 24 | FA | A1 | 0-0 | SPARE | D06240J | A12 | \$D | *1 | D00881A | REF | ** | | ALL | | |
| AK13 | 24 | FA | A1 | 0-0 | SPARE | D06240J | A13 | \$D | *1 | D00881A | REF | ** | | ALL | | |
| AK14 | 24 | FA | A1 | 0-0 | SPARE | D06240J | A14 | \$D | *1 | D00881A | REF | ** | | ALL | | |
| AK15 | 24 | FA | A1 | 0-0 | 73-33-11 | D06240J | A15 | \$D | *1 | GD00083 | A.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| AK15 | 24 | FA | A1 | 0-0 | 73-33-11 | D06240J | A15 | \$D | *1 | GDX0002 | A.. | 2 | | 155-157, 165-199, 277-299 | | |
| AK16 | 24 | FA | A1 | 0-0 | 73-31-11 | D06240J | A16 | \$D | *1 | GD00091 | S.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| AK16 | 24 | FA | A1 | 0-0 | 73-31-11 | D06240J | A16 | \$D | *1 | GDX0002 | S.. | 2 | | 155-157, 165-199, 277-299 | | |
| AK17 | 24 | FA | A1 | 0-0 | 76-11-11 | D06240J | A17 | \$D | *1 | D00881B | F13 | | | ALL | | |
| AK18 | 24 | FA | A1 | 0-0 | SPARE | D06240J | A18 | \$D | *1 | D00881A | REF | ** | | ALL | | |
| AK19 | 24 | FA | A1 | 0-0 | SPARE | D06240J | A19 | \$D | *1 | D00881A | REF | ** | | ALL | | |
| AK20 | 24 | FA | A1 | 0-0 | 99-99-99 | D06240J | A20 | \$D | *1 | D00881A | REF | | | ALL | | |
| AM01 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A01 | \$D | *1 | GD00155 | S.. | 2 | | ALL | | |
| AM02 | 24 | FA | A2 | 0-0 | 73-31-11 | D06240J | A02 | \$D | *1 | D00883A | J08 | | | ALL | | |
| AM03 | 24 | FA | A2 | 0-0 | 73-31-11 | D06240J | A03 | \$D | *1 | D00883A | J09 | | | ALL | | |
| AM04 | 24 | FA | A2 | 0-0 | 73-31-11 | D06240J | A04 | \$D | *1 | D00883A | J07 | | | ALL | | |
| AM05 | 24 | FA | A2 | 0-0 | 79-32-11 | D06240J | A05 | \$D | *1 | D00883B | H02 | | | ALL | | |
| AM06 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A06 | \$D | *1 | D00883A | REF | ** | | ALL | | |
| AM07 | 24 | FA | A2 | 0-0 | 79-32-11 | D06240J | A07 | \$D | *1 | TB0237X | A015 | BJ | | ALL | | |
| AM08 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A08 | \$D | *1 | D00883A | REF | ** | | ALL | | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 1
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| AM09 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A09 | \$D | *1 | D00883A | REF | ** | | ALL | | |
| AM10 | 24 | FA | A2 | 0-0 | 79-32-11 | D06240J | A10 | \$D | *1 | D00883B | G01 | | | ALL | | |
| AM11 | 24 | FA | A2 | 0-0 | 73-34-11 | D06240J | A11 | \$D | *1 | D00883A | J11 | | | ALL | | |
| AM12 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A12 | \$D | *1 | D00883A | REF | ** | | 050-099, 275-299 | | |
| AM12 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A12 | \$D | *1 | D00883A | H11 | | | 150-199 | | |
| AM13 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A13 | \$D | *1 | D00883A | REF | ** | | 050-099, 275-299 | | |
| AM13 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A13 | \$D | *1 | D00883A | H10 | | | 150-199 | | |
| AM14 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A14 | \$D | *1 | D00883A | REF | ** | | ALL | | |
| AM15 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A15 | \$D | *1 | D00883A | REF | ** | | ALL | | |
| AM16 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A16 | \$D | *1 | D00883A | REF | ** | | ALL | | |
| AM17 | 24 | FA | A2 | 0-0 | 76-11-11 | D06240J | A17 | \$D | *1 | D00883B | F13 | | | ALL | | |
| AM18 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A18 | \$D | *1 | D00883A | REF | ** | | ALL | | |
| AM19 | 24 | FA | A2 | 0-0 | SPARE | D06240J | A19 | \$D | *1 | D00883A | REF | ** | | ALL | | |
| AM20 | 24 | FA | A2 | 0-0 | 99-99-99 | D06240J | A20 | \$D | *1 | D00883A | REF | | | ALL | | |
| BK01 | 24 | FA | B2 | 0-0 | SPARE | D06244J | A01 | \$D | *3 | GD00085 | S.. | 2 | | ALL | | |
| BK02 | 24 | FA | B2 | 0-0 | SPARE | D06244J | A02 | \$D | *3 | D00881A | REF | ** | | ALL | | |
| BK03 | 24 | FA | B2 | 0-0 | 29-33-11 | D06244J | A03 | \$D | *3 | D00881A | F03 | | | ALL | | |
| BK04 | 24 | FA | B2 | 0-0 | 29-33-11 | D06244J | A04 | \$D | *3 | D00881A | F04 | | | ALL | | |
| BK05 | 24 | FA | B2 | 0-0 | 29-33-11 | D06244J | A05 | \$D | *3 | D00881E | A03 | | | ALL | | |
| BK06 | 24 | FA | B2 | 0-0 | 29-33-11 | D06244J | A06 | \$D | *3 | D00881D | B06 | | | ALL | | |
| BK07 | 24 | FA | B2 | 0-0 | 29-32-11 | D06244J | A07 | \$D | *3 | D00881D | D04 | | | ALL | | |
| BK08 | 24 | FA | B2 | 0-0 | 29-32-11 | D06244J | A08 | \$D | *3 | D00881D | D05 | | | ALL | | |
| BK09 | 24 | FA | B2 | 0-0 | SPARE | D06244J | A09 | \$D | *3 | D00881A | REF | ** | | ALL | | |
| BK10 | 24 | FA | B2 | 0-0 | SPARE | D06244J | A10 | \$D | *3 | D00881A | REF | ** | | ALL | | |
| BK11 | 24 | FA | B2 | 0-0 | SPARE | D06244J | A11 | \$D | *3 | D00881A | REF | ** | | ALL | | |
| BK12 | 24 | FA | B2 | 0-0 | 29-31-11 | D06244J | A12 | \$D | *3 | D00881B | H04 | | | ALL | | |
| BK13 | 24 | FA | B2 | 0-0 | 29-31-11 | D06244J | A13 | \$D | *3 | GD00091 | A.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| BK13 | 24 | FA | B2 | 0-0 | 29-31-11 | D06244J | A13 | \$D | *3 | GDX0002 | A.. | 2 | | 155-157, 165-199, 277-299 | | |
| BK14 | 24 | FA | B2 | 0-0 | 21-64-11 | D06244J | A14 | \$D | *3 | GD00083 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| BK14 | 24 | FA | B2 | 0-0 | 21-64-11 | D06244J | A14 | \$D | *3 | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 | | |
| BK15 | 24 | FA | B2 | 0-0 | SPARE | D06244J | A15 | \$D | *3 | D00881A | REF | ** | | 050-099, 155-199, 276-299 | | |
| BK15 | 24 | FA | B2 | 0-0 | 21-64-11 | D06244J | A15 | \$D | *3 | D00881E | E05 | | | 150-154, 275 | | |
| BK16 | 24 | FA | B2 | 0-0 | 21-64-11 | D06244J | A16 | \$D | *3 | TB0237Z | 10 | BJ | | ALL | | |
| BK17 | 24 | FA | B2 | 0-0 | SPARE | D06244J | A17 | \$D | *3 | D00881A | REF | ** | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| BK18 | 24 | FA | B2 | | 0-0 | SPARE | D06244J | A18 | \$D | *3 | D00881A | REF | ** | | ALL |
| BK19 | 24 | FA | B2 | | 0-0 | 21-64-11 | D06244J | A19 | \$D | *3 | D00881E | E05 | | | 050-099, 155-199, 276-299 |
| BK19 | 24 | FA | B2 | | 0-0 | SPARE | D06244J | A19 | \$D | *3 | D00881A | REF | ** | | 150-154, 275 |
| BK20 | 24 | FA | B2 | | 0-0 | 99-99-99 | D06244J | A20 | \$D | *3 | D00881A | REF | | | ALL |
| BM01 | 24 | FA | B1 | | 0-0 | 99-99-99 | D06244J | A01 | \$D | *3 | D00883A | REF | | | ALL |
| BM02 | 24 | FA | B1 | | 0-0 | SPARE | D06244J | A02 | \$D | *3 | D00883A | REF | ** | | ALL |
| BM03 | 24 | FA | B1 | | 0-0 | 29-33-11 | D06244J | A03 | \$D | *3 | D00883A | F03 | | | ALL |
| BM04 | 24 | FA | B1 | | 0-0 | 29-33-11 | D06244J | A04 | \$D | *3 | D00883A | F04 | | | ALL |
| BM05 | 24 | FA | B1 | | 0-0 | 29-33-11 | D06244J | A05 | \$D | *3 | D00883E | A03 | | | ALL |
| BM06 | 24 | FA | B1 | | 0-0 | 29-33-11 | D06244J | A06 | \$D | *3 | D00883D | B06 | | | ALL |
| BM07 | 24 | FA | B1 | | 0-0 | SPARE | D06244J | A07 | \$D | *3 | D00883A | REF | ** | | ALL |
| BM08 | 24 | FA | B1 | | 0-0 | SPARE | D06244J | A08 | \$D | *3 | D00883A | REF | ** | | ALL |
| BM09 | 24 | FA | B1 | | 0-0 | SPARE | D06244J | A09 | \$D | *3 | D00883A | REF | ** | | ALL |
| BM10 | 24 | FA | B1 | | 0-0 | SPARE | D06244J | A10 | \$D | *3 | D00883A | REF | ** | | ALL |
| BM11 | 24 | FA | B1 | | 0-0 | SPARE | D06244J | A11 | \$D | *3 | D00883A | REF | ** | | ALL |
| BM12 | 24 | FA | B1 | | 0-0 | 29-31-11 | D06244J | A12 | \$D | *3 | D00883B | H04 | | | ALL |
| BM13 | 24 | FA | B1 | | 0-0 | SPARE | D06244J | A13 | \$D | *3 | D00883A | REF | ** | | ALL |
| BM14 | 24 | FA | B1 | | 0-0 | SPARE | D06244J | A14 | \$D | *3 | D00883A | REF | ** | | ALL |
| BM15 | 24 | FA | B1 | | 0-0 | 21-64-11 | D06244J | A15 | \$D | *3 | D00883E | E05 | | | 050-099, 155-199, 276-299 |
| BM15 | 24 | FA | B1 | | 0-0 | SPARE | D06244J | A15 | \$D | *3 | D00883A | REF | ** | | 150-154, 275 |
| BM16 | 24 | FA | B1 | | 0-0 | SPARE | D06244J | A16 | \$D | *3 | D00883A | REF | ** | | ALL |
| BM17 | 24 | FA | B1 | | 0-0 | 21-64-11 | D06244J | A17 | \$D | *3 | GD00153 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 |
| BM17 | 24 | FA | B1 | | 0-0 | 21-64-11 | D06244J | A17 | \$D | *3 | GDX0001 | D.. | 2 | | 155-157, 165-199, 277-299 |
| BM18 | 24 | FA | B1 | | 0-0 | 21-64-11 | D06244J | A18 | \$D | *3 | TB0237Z | 10 | BJ | | ALL |
| BM19 | 24 | FA | B1 | | 0-0 | SPARE | D06244J | A19 | \$D | *3 | D00883A | REF | ** | | 050-099, 155-199, 276-299 |
| BM19 | 24 | FA | B1 | | 0-0 | 21-64-11 | D06244J | A19 | \$D | *3 | D00883E | E05 | | | 150-154, 275 |
| BM20 | 24 | FA | B1 | | 0-0 | 99-99-99 | D06244J | A20 | \$D | *3 | GD00155 | REF | | | 050-099, 150-154, 275-276 |
| BM20 | 24 | FA | B1 | | 0-0 | 99-99-99 | D06244J | A20 | \$D | *3 | D00883A | REF | | | 155-199, 277-299 |
| CK01 | 24 | FA | C1 | | 0-0 | 99-99-99 | D06206J | A01 | \$D | *5 | D00881A | REF | | | ALL |
| CK02 | 24 | FA | C1 | | 0-0 | 29-21-32 | D06206J | A02 | \$D | *5 | D00881F | K10 | | | ALL |
| CK03 | 24 | FA | C1 | | 0-0 | 21-31-21 | D06206J | A03 | \$D | *5 | D00881E | F13 | | | ALL |
| CK04 | 24 | FA | C1 | | 0-0 | 24-51-13 | D06206J | A04 | \$D | *5 | D00881A | E05 | | | ALL |
| CK05 | 24 | FA | C1 | | 0-0 | 27-13-11 | D06206J | A05 | \$D | *5 | D00881E | J06 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|------|----------|---------|-------|------|------|---------|-------|------|------|------------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| CK06 | 24 | FA | C1 | | 0-0 | 29-11-22 | D06206J | A06 | \$D | *5 | D00881F | K02 | | | ALL |
| CK07 | 24 | FA | C1 | | 0-0 | 29-11-31 | D06206J | A07 | \$D | *5 | D00881A | G11 | | | ALL |
| CK08 | 24 | FA | C1 | | 0-0 | SPARE | D06206J | A08 | \$D | *5 | D00881A | REF | ** | | ALL |
| CK09 | 24 | FA | C1 | | 0-0 | SPARE | D06206J | A09 | \$D | *5 | D00881B | REF | ** | | 050-099, 275-276 |
| CK09 | 24 | FA | C1 | | 0-0 | 73-14-11 | D06206J | A09 | \$D | *5 | D00881B | F05 | | | 150-199 |
| CK09 | 24 | FA | C1 | | 0-0 | SPARE | D06206J | A09 | \$D | *5 | D00881A | REF | ** | | 277-299 |
| CK10 | 24 | FA | C1 | | 0-0 | SPARE | D06206J | A10 | \$D | *5 | D00881A | REF | ** | | ALL |
| CK11 | 24 | FA | C1 | | 0-0 | 36-11-31 | D06206J | A11 | \$D | *5 | D00881B | G13 | | | ALL |
| CK12 | 24 | FA | C1 | | 0-0 | 29-32-11 | D06206J | A12 | \$D | *5 | D00881A | K08 | | | ALL |
| CK13 | 24 | FA | C1 | | 0-0 | 29-32-11 | D06206J | A13 | \$D | *5 | D00881B | K08 | | | ALL |
| CK14 | 24 | FA | C1 | | 0-0 | 30-21-11 | D06206J | A14 | \$D | *5 | D00881E | C14 | | | ALL |
| CK15 | 24 | FA | C1 | | 0-0 | SPARE | D06206J | A15 | \$D | *5 | D00881A | REF | ** | | 050-099, 150-199 |
| CK15 | 24 | FA | C1 | | 0-0 | 30-21-11 | D06206J | A15 | \$D | *5 | D00881B | H12 | | | 275-299 |
| CK16 | 24 | FA | C1 | | 0-0 | SPARE | D06206J | A16 | \$D | *5 | D00881A | REF | ** | | ALL |
| CK17 | 24 | FA | C1 | | 0-0 | SPARE | D06206J | A17 | \$D | *5 | D00881A | REF | ** | | ALL |
| CK18 | 24 | FA | C1 | | 0-0 | SPARE | D06206J | A18 | \$D | *5 | D00881A | REF | ** | | ALL |
| CK19 | 24 | FA | C1 | | 0-0 | 28-31-11 | D06206J | A19 | \$D | *5 | D00881A | H09 | | | 050-099, 155-199, 276-299 |
| CK19 | 24 | FA | C1 | | 0-0 | SPARE | D06206J | A19 | \$D | *5 | D00881A | REF | ** | | 150-154, 275 |
| CK20 | 24 | FA | C1 | | 0-0 | 99-99-99 | D06206J | A20 | \$D | *5 | GD00085 | REF | | | 050-099, 150-154, 275-276 |
| CK20 | 24 | FA | C1 | | 0-0 | 99-99-99 | D06206J | A20 | \$D | *5 | D00881A | REF | | | 155-199, 277-299 |
| CM01 | 24 | FA | C2 | | 0-0 | SPARE | D06206J | A01 | \$D | *5 | GD00155 | S.. | 2 | | ALL |
| CM02 | 24 | FA | C2 | | 0-0 | 29-21-32 | D06206J | A02 | \$D | *5 | D00883F | K10 | | | ALL |
| CM03 | 24 | FA | C2 | | 0-0 | 21-31-21 | D06206J | A03 | \$D | *5 | D00883E | F13 | | | ALL |
| CM04 | 24 | FA | C2 | | 0-0 | 24-51-13 | D06206J | A04 | \$D | *5 | D00883A | E05 | | | ALL |
| CM05 | 24 | FA | C2 | | 0-0 | 27-13-11 | D06206J | A05 | \$D | *5 | D00883E | J06 | | | ALL |
| CM06 | 24 | FA | C2 | | 0-0 | 29-11-22 | D06206J | A06 | \$D | *5 | D00883F | K02 | | | ALL |
| CM07 | 24 | FA | C2 | | 0-0 | 29-11-31 | D06206J | A07 | \$D | *5 | D00883A | G11 | | | ALL |
| CM08 | 24 | FA | C2 | | 0-0 | SPARE | D06206J | A08 | \$D | *5 | D00883A | REF | ** | | ALL |
| CM09 | 24 | FA | C2 | | 0-0 | SPARE | D06206J | A09 | \$D | *5 | D00883A | REF | ** | | 050-099, 275-299 |
| CM09 | 24 | FA | C2 | | 0-0 | 73-14-11 | D06206J | A09 | \$D | *5 | D00883B | F05 | | | 150-199 |
| CM10 | 24 | FA | C2 | | 0-0 | SPARE | D06206J | A10 | \$D | *5 | D00883A | REF | ** | | ALL |
| CM11 | 24 | FA | C2 | | 0-0 | 36-11-31 | D06206J | A11 | \$D | *5 | D00883B | G13 | | | ALL |
| CM12 | 24 | FA | C2 | | 0-0 | 29-32-11 | D06206J | A12 | \$D | *5 | D00883A | K08 | | | ALL |
| CM13 | 24 | FA | C2 | | 0-0 | 29-32-11 | D06206J | A13 | \$D | *5 | D00883B | K08 | | | ALL |
| CM14 | 24 | FA | C2 | | 0-0 | 30-21-11 | D06206J | A14 | \$D | *5 | D00883E | C14 | | | ALL |
| CM15 | 24 | FA | C2 | | 0-0 | SPARE | D06206J | A15 | \$D | *5 | D00883A | REF | ** | | 050-099, 150-199 |
| CM15 | 24 | FA | C2 | | 0-0 | 30-21-11 | D06206J | A15 | \$D | *5 | D00883B | H12 | | | 275-299 |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| CM16 | 24 | FA | C2 | | 0-0 | SPARE | D06206J | A16 | \$D | *5 | D00883A | REF | ** | | ALL |
| CM17 | 24 | FA | C2 | | 0-0 | SPARE | D06206J | A17 | \$D | *5 | D00883A | REF | ** | | ALL |
| CM18 | 24 | FA | C2 | | 0-0 | SPARE | D06206J | A18 | \$D | *5 | D00883A | REF | ** | | ALL |
| CM19 | 24 | FA | C2 | | 0-0 | 28-31-11 | D06206J | A19 | \$D | *5 | D00883A | H09 | | | 050-099, 155-199, 276-299 |
| CM19 | 24 | FA | C2 | | 0-0 | SPARE | D06206J | A19 | \$D | *5 | D00883A | REF | ** | | 150-154, 275 |
| CM20 | 24 | FA | C2 | | 0-0 | 99-99-99 | D06206J | A20 | \$D | *5 | D00883A | REF | | | ALL |
| DK01 | 24 | FA | D2 | | 0-0 | SPARE | D06246J | A01 | \$D | *7 | GD00085 | S.. | 2 | *1 | ALL |
| DK02 | 24 | FA | D2 | | 0-0 | 36-11-51 | D06246J | A02 | \$D | *7 | D00881E | K03 | | | ALL |
| DK03 | 24 | FA | D2 | | 0-0 | 36-11-52 | D06246J | A03 | \$D | *7 | D00881E | K06 | | | ALL |
| DK04 | 24 | FA | D2 | | 0-0 | 36-22-11 | D06246J | A04 | \$D | *7 | D00881E | K07 | | | ALL |
| DK05 | 24 | FA | D2 | | 0-0 | 36-22-11 | D06246J | A05 | \$D | *7 | D00881E | K11 | | | ALL |
| DK06 | 24 | FA | D2 | | 0-0 | 36-21-11 | D06246J | A06 | \$D | *7 | D00881D | H13 | | | ALL |
| DK07 | 24 | FA | D2 | | 0-0 | 36-21-11 | D06246J | A07 | \$D | *7 | GD00091 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 |
| DK07 | 24 | FA | D2 | | 0-0 | 36-21-11 | D06246J | A07 | \$D | *7 | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 |
| DK08 | 24 | FA | D2 | | 0-0 | 36-11-62 | D06246J | A08 | \$D | *7 | D00881E | K02 | | | ALL |
| DK09 | 24 | FA | D2 | | 0-0 | 36-11-61 | D06246J | A09 | \$D | *7 | D00881E | K10 | | | ALL |
| DK10 | 24 | FA | D2 | | 0-0 | SPARE | D06246J | A10 | \$D | *7 | D00881A | REF | ** | | 050-099, 275-299 |
| DK10 | 24 | FA | D2 | | 0-0 | SPARE | D06246J | A10 | \$D | *7 | D00881B | H06 | | | 150-199 |
| DK11 | 24 | FA | D2 | | 0-0 | SPARE | D06246J | A11 | \$D | *7 | D00881A | REF | ** | | ALL |
| DK12 | 24 | FA | D2 | | 0-0 | 21-44-21 | D06246J | A12 | \$D | *7 | D00881F | C06 | | | ALL |
| DK13 | 24 | FA | D2 | | 0-0 | 73-21-14 | D06246J | A13 | \$D | *7 | D00881A | E08 | | | ALL |
| DK14 | 24 | FA | D2 | | 0-0 | 73-21-18 | D06246J | A14 | \$D | *7 | D00881F | J10 | | | ALL |
| DK15 | 24 | FA | D2 | | 0-0 | SPARE | D06246J | A15 | \$D | *7 | D00881D | A02 | | | 050-099 |
| DK15 | 24 | FA | D2 | | 0-0 | SPARE | D06246J | A15 | \$D | *7 | D00881A | REF | ** | | 150-199, 275-299 |
| DK16 | 24 | FA | D2 | | 0-0 | 32-42-11 | D06246J | A16 | \$D | *7 | D00881E | J05 | | | ALL |
| DK17 | 24 | FA | D2 | | 0-0 | 21-58-11 | D06246J | A17 | \$D | *7 | D00881D | A03 | | | ALL |
| DK18 | 24 | FA | D2 | | 0-0 | 21-52-31 | D06246J | A18 | \$D | *7 | D00881A | E15 | | | ALL |
| DK19 | 24 | FA | D2 | | 0-0 | 21-52-31 | D06246J | A19 | \$D | *7 | D00881A | D15 | | | ALL |
| DK20 | 24 | FA | D2 | | 0-0 | 99-99-99 | D06246J | A20 | \$D | *7 | D00881A | REF | | | ALL |
| DL01 | 24 | FB | D4 | | 0-0 | SPARE | D06246J | B01 | \$D | *7 | GD00085 | S.. | 2 | *1 | ALL |
| DL02 | 24 | FB | D4 | | 0-0 | 36-11-61 | D06246J | B02 | \$D | *7 | D00881B | H09 | | | ALL |
| DL03 | 24 | FB | D4 | | 0-0 | 21-28-11 | D06246J | B03 | \$D | *7 | D00881E | H14 | | | ALL |
| DL04 | 24 | FB | D4 | | 0-0 | 21-28-11 | D06246J | B04 | \$D | *7 | D00881E | H15 | | | ALL |
| DL05 | 24 | FB | D4 | | 0-0 | 21-52-31 | D06246J | B05 | \$D | *7 | D00881F | A07 | | | ALL |
| DL06 | 24 | FB | D4 | | 0-0 | 21-52-31 | D06246J | B06 | \$D | *7 | D00881F | A08 | | | ALL |
| DL07 | 24 | FB | D4 | | 0-0 | 21-52-31 | D06246J | B07 | \$D | *7 | D00881F | C01 | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W2000
Page 5
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| DL08 | 24 | FB | D4 | 0-0 | 21-52-31 | D06246J | B08 | \$D | *7 | D00881F | D01 | | | ALL | | |
| DL09 | 24 | FB | D4 | 0-0 | 21-52-31 | D06246J | B09 | \$D | *7 | D00881D | D13 | | | ALL | | |
| DL10 | 24 | FB | D4 | 0-0 | 21-52-31 | D06246J | B10 | \$D | *7 | D00881D | D14 | | | ALL | | |
| DL11 | 24 | FB | D4 | 0-0 | 21-52-11 | D06246J | B11 | \$D | *7 | TB0237Z | 17 | BJ | | ALL | | |
| DL12 | 24 | FB | D4 | 0-0 | 21-52-11 | D06246J | B12 | \$D | *7 | D00881E | J09 | | | ALL | | |
| DL13 | 24 | FB | D4 | 0-0 | 21-52-11 | D06246J | B13 | \$D | *7 | GD00081 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| DL13 | 24 | FB | D4 | 0-0 | 21-52-11 | D06246J | B13 | \$D | *7 | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 | | |
| DL14 | 24 | FB | D4 | 0-0 | 21-58-11 | D06246J | B14 | \$D | *7 | D00881D | A04 | | | ALL | | |
| DL15 | 24 | FB | D4 | 0-0 | 21-52-31 | D06246J | B15 | \$D | *7 | D00881A | F14 | | | ALL | | |
| DL16 | 24 | FB | D4 | 0-0 | 21-52-31 | D06246J | B16 | \$D | *7 | D00881A | E14 | | | ALL | | |
| DL17 | 24 | FB | D4 | 0-0 | SPARE | D06246J | B17 | \$D | *7 | D00881A | REF | ** | | ALL | | |
| DL18 | 24 | FB | D4 | 0-0 | SPARE | D06246J | B18 | \$D | *7 | D00881A | REF | ** | | ALL | | |
| DL19 | 24 | FB | D4 | 0-0 | SPARE | D06246J | B19 | \$D | *7 | D00881A | REF | ** | | ALL | | |
| DL20 | 24 | FB | D4 | 0-0 | 99-99-99 | D06246J | B20 | \$D | *7 | D00881A | REF | | | ALL | | |
| DM01 | 24 | FA | D1 | 0-0 | 99-99-99 | D06246J | A01 | \$D | *7 | D00883A | REF | | | ALL | | |
| DM02 | 24 | FA | D1 | 0-0 | 36-11-51 | D06246J | A02 | \$D | *7 | D00883E | K03 | | | ALL | | |
| DM03 | 24 | FA | D1 | 0-0 | 36-11-52 | D06246J | A03 | \$D | *7 | D00883E | K06 | | | ALL | | |
| DM04 | 24 | FA | D1 | 0-0 | 36-22-11 | D06246J | A04 | \$D | *7 | D00883E | K07 | | | ALL | | |
| DM05 | 24 | FA | D1 | 0-0 | 36-22-11 | D06246J | A05 | \$D | *7 | D00883E | K11 | | | ALL | | |
| DM06 | 24 | FA | D1 | 0-0 | SPARE | D06246J | A06 | \$D | *7 | D00883A | REF | ** | | ALL | | |
| DM07 | 24 | FA | D1 | 0-0 | SPARE | D06246J | A07 | \$D | *7 | D00883A | REF | ** | | ALL | | |
| DM08 | 24 | FA | D1 | 0-0 | 36-11-62 | D06246J | A08 | \$D | *7 | D00883E | K02 | | | ALL | | |
| DM09 | 24 | FA | D1 | 0-0 | 36-11-61 | D06246J | A09 | \$D | *7 | D00883E | K10 | | | ALL | | |
| DM10 | 24 | FA | D1 | 0-0 | SPARE | D06246J | A10 | \$D | *7 | D00883A | REF | ** | | 050-099, 275-299 | | |
| DM10 | 24 | FA | D1 | 0-0 | SPARE | D06246J | A10 | \$D | *7 | D00883B | H06 | | | 150-199 | | |
| DM11 | 24 | FA | D1 | 0-0 | SPARE | D06246J | A11 | \$D | *7 | D00883A | REF | ** | | ALL | | |
| DM12 | 24 | FA | D1 | 0-0 | 21-44-21 | D06246J | A12 | \$D | *7 | D00883F | C06 | | | ALL | | |
| DM13 | 24 | FA | D1 | 0-0 | SPARE | D06246J | A13 | \$D | *7 | D00883A | REF | ** | | ALL | | |
| DM14 | 24 | FA | D1 | 0-0 | 73-21-18 | D06246J | A14 | \$D | *7 | D00883F | J10 | | | ALL | | |
| DM15 | 24 | FA | D1 | 0-0 | SPARE | D06246J | A15 | \$D | *7 | D00883D | A02 | | | 050-099 | | |
| DM15 | 24 | FA | D1 | 0-0 | SPARE | D06246J | A15 | \$D | *7 | D00883A | REF | ** | | 150-199, 275-299 | | |
| DM16 | 24 | FA | D1 | 0-0 | 32-42-11 | D06246J | A16 | \$D | *7 | D00883E | J05 | | | ALL | | |
| DM17 | 24 | FA | D1 | 0-0 | 21-58-11 | D06246J | A17 | \$D | *7 | D00883D | A03 | | | ALL | | |
| DM18 | 24 | FA | D1 | 0-0 | SPARE | D06246J | A18 | \$D | *7 | D00883A | REF | ** | | ALL | | |
| DM19 | 24 | FA | D1 | 0-0 | SPARE | D06246J | A19 | \$D | *7 | D00883A | REF | ** | | ALL | | |
| DM20 | 24 | FA | D1 | 0-0 | 99-99-99 | D06246J | A20 | \$D | *7 | D00883A | REF | | | ALL | | |
| DN01 | 24 | FB | D3 | 0-0 | 99-99-99 | D06246J | B01 | \$D | *7 | D00883A | REF | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| DN02 | 24 | FB | D3 | | 0-0 | 36-11-61 | D06246J | B02 | \$D | *7 | D00883B | H09 | | | ALL |
| DN03 | 24 | FB | D3 | | 0-0 | 21-28-11 | D06246J | B03 | \$D | *7 | D00883E | H14 | | | ALL |
| DN04 | 24 | FB | D3 | | 0-0 | 21-28-11 | D06246J | B04 | \$D | *7 | D00883E | H15 | | | ALL |
| DN05 | 24 | FB | D3 | | 0-0 | SPARE | D06246J | B05 | \$D | *7 | D00883A | REF | ** | | ALL |
| DN06 | 24 | FB | D3 | | 0-0 | SPARE | D06246J | B06 | \$D | *7 | D00883A | REF | ** | | ALL |
| DN07 | 24 | FB | D3 | | 0-0 | SPARE | D06246J | B07 | \$D | *7 | D00883A | REF | ** | | ALL |
| DN08 | 24 | FB | D3 | | 0-0 | SPARE | D06246J | B08 | \$D | *7 | D00883A | REF | ** | | ALL |
| DN09 | 24 | FB | D3 | | 0-0 | SPARE | D06246J | B09 | \$D | *7 | D00883A | REF | ** | | ALL |
| DN10 | 24 | FB | D3 | | 0-0 | SPARE | D06246J | B10 | \$D | *7 | D00883A | REF | ** | | ALL |
| DN11 | 24 | FB | D3 | | 0-0 | SPARE | D06246J | B11 | \$D | *7 | D00883A | REF | ** | | ALL |
| DN12 | 24 | FB | D3 | | 0-0 | SPARE | D06246J | B12 | \$D | *7 | D00883A | REF | ** | | ALL |
| DN13 | 24 | FB | D3 | | 0-0 | SPARE | D06246J | B13 | \$D | *7 | D00883A | REF | ** | | ALL |
| DN14 | 24 | FB | D3 | | 0-0 | 21-58-11 | D06246J | B14 | \$D | *7 | D00883D | A04 | | | ALL |
| DN15 | 24 | FB | D3 | | 0-0 | SPARE | D06246J | B15 | \$D | *7 | D00883A | REF | ** | | ALL |
| DN16 | 24 | FB | D3 | | 0-0 | SPARE | D06246J | B16 | \$D | *7 | D00883A | REF | ** | | ALL |
| DN17 | 24 | FB | D3 | | 0-0 | 21-64-11 | D06246J | B17 | \$D | *7 | GD00169 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 |
| DN17 | 24 | FB | D3 | | 0-0 | 21-64-11 | D06246J | B17 | \$D | *7 | GDX0001 | D.. | 2 | | 155-157, 165-199, 277-299 |
| DN18 | 24 | FB | D3 | | 0-0 | 21-64-11 | D06246J | B18 | \$D | *7 | TB0237Z | 10 | BJ | | ALL |
| DN19 | 24 | FB | D3 | | 0-0 | 21-64-11 | D06246J | B19 | \$D | *7 | D00883F | G09 | | | ALL |
| DN20 | 24 | FB | D3 | | 0-0 | 99-99-99 | D06246J | B20 | \$D | *7 | D00883A | REF | | | ALL |
| EK01 | 24 | FA | E1 | | 0-0 | 99-99-99 | D06208J | A01 | \$D | *9 | D00881A | REF | | | ALL |
| EK02 | 24 | FA | E1 | | 0-0 | 27-38-11 | D06208J | A02 | \$D | *9 | D00881E | H06 | | | ALL |
| EK03 | 24 | FA | E1 | | 0-0 | 27-38-11 | D06208J | A03 | \$D | *9 | GD00091 | A.. | 2 | | 050-099, 150-154, 162-164, 275-276 |
| EK03 | 24 | FA | E1 | | 0-0 | 27-38-11 | D06208J | A03 | \$D | *9 | GDX0002 | A.. | 2 | | 155-157, 165-199, 277-299 |
| EK04 | 24 | FA | E1 | | 0-0 | 27-38-11 | D06208J | A04 | \$D | *9 | D00881E | H07 | | | ALL |
| EK05 | 24 | FA | E1 | | 0-0 | SPARE | D06208J | A05 | \$D | *9 | D00881A | REF | ** | | ALL |
| EK06 | 24 | FA | E1 | | 0-0 | 28-22-21 | D06208J | A06 | \$D | *9 | D00881E | D05 | | | ALL |
| EK07 | 24 | FA | E1 | | 0-0 | 77-35-11 | D06208J | A07 | \$D | *9 | D00881E | A08 | | | ALL |
| EK08 | 24 | FA | E1 | | 0-0 | 73-33-11 | D06208J | A08 | \$D | *9 | D00881A | J10 | | | ALL |
| EK09 | 24 | FA | E1 | | 0-0 | 36-22-21 | D06208J | A09 | \$D | *9 | D00881D | H15 | | | ALL |
| EK10 | 24 | FA | E1 | | 0-0 | 36-22-21 | D06208J | A10 | \$D | *9 | D00881D | H14 | | | ALL |
| EK11 | 24 | FA | E1 | | 0-0 | 79-33-11 | D06208J | A11 | \$D | *9 | D00881A | H03 | | | ALL |
| EK12 | 24 | FA | E1 | | 0-0 | 29-32-11 | D06208J | A12 | \$D | *9 | D00881F | G04 | | | ALL |
| EK13 | 24 | FA | E1 | | 0-0 | SPARE | D06208J | A13 | \$D | *9 | D00881A | REF | ** | | ALL |
| EK14 | 24 | FA | E1 | | 0-0 | SPARE | D06208J | A14 | \$D | *9 | D00881A | REF | ** | | ALL |

WIRE LIST

D280T132

91-21-11
Section W2000
Page 7
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| EK15 | 24 | FA | E1 | 0-0 | 77-12-12 | D06208J | A15 | \$D | *9 | GD00085 | S.. | 2 | | ALL | | |
| EK16 | 24 | FA | E1 | 0-0 | 77-12-12 | D06208J | A16 | \$D | *9 | D00881A | J05 | | | ALL | | |
| EK17 | 24 | FA | E1 | 0-0 | 77-12-12 | D06208J | A17 | \$D | *9 | D00881A | J06 | | | ALL | | |
| EK18 | 24 | FA | E1 | 0-0 | 77-12-12 | D06208J | A18 | \$D | *9 | GD00085 | S.. | 2 | | ALL | | |
| EK19 | 24 | FA | E1 | 0-0 | SPARE | D06208J | A19 | \$D | *9 | D00881A | REF | ** | | ALL | | |
| EK20 | 24 | FA | E1 | 0-0 | 99-99-99 | D06208J | A20 | \$D | *9 | D00881A | REF | | | ALL | | |
| EM01 | 24 | FA | E2 | 0-0 | SPARE | D06208J | A01 | \$D | *9 | GD00155 | S.. | 2 | | ALL | | |
| EM02 | 24 | FA | E2 | 0-0 | 27-38-11 | D06208J | A02 | \$D | *9 | D00883E | H06 | | | ALL | | |
| EM03 | 24 | FA | E2 | 0-0 | SPARE | D06208J | A03 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| EM04 | 24 | FA | E2 | 0-0 | 27-38-11 | D06208J | A04 | \$D | *9 | D00883E | H07 | | | ALL | | |
| EM05 | 24 | FA | E2 | 0-0 | 27-38-11 | D06208J | A05 | \$D | *9 | GD00169 | A.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| EM05 | 24 | FA | E2 | 0-0 | 27-38-11 | D06208J | A05 | \$D | *9 | GDX0001 | A.. | 2 | | 155-157, 165-199, 277-299 | | |
| EM06 | 24 | FA | E2 | 0-0 | 28-22-21 | D06208J | A06 | \$D | *9 | D00883E | D05 | | | ALL | | |
| EM07 | 24 | FA | E2 | 0-0 | 77-35-11 | D06208J | A07 | \$D | *9 | D00883E | A08 | | | ALL | | |
| EM08 | 24 | FA | E2 | 0-0 | 73-33-11 | D06208J | A08 | \$D | *9 | D00883A | J10 | | | ALL | | |
| EM09 | 24 | FA | E2 | 0-0 | SPARE | D06208J | A09 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| EM10 | 24 | FA | E2 | 0-0 | SPARE | D06208J | A10 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| EM11 | 24 | FA | E2 | 0-0 | 79-33-11 | D06208J | A11 | \$D | *9 | D00883A | H03 | | | ALL | | |
| EM12 | 24 | FA | E2 | 0-0 | 29-32-11 | D06208J | A12 | \$D | *9 | D00883F | G04 | | | ALL | | |
| EM13 | 24 | FA | E2 | 0-0 | SPARE | D06208J | A13 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| EM14 | 24 | FA | E2 | 0-0 | SPARE | D06208J | A14 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| EM15 | 24 | FA | E2 | 0-0 | SPARE | D06208J | A15 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| EM16 | 24 | FA | E2 | 0-0 | 77-12-12 | D06208J | A16 | \$D | *9 | D00883A | J05 | | | ALL | | |
| EM17 | 24 | FA | E2 | 0-0 | 77-12-12 | D06208J | A17 | \$D | *9 | D00883A | J06 | | | ALL | | |
| EM18 | 24 | FA | E2 | 0-0 | SPARE | D06208J | A18 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| EM19 | 24 | FA | E2 | 0-0 | SPARE | D06208J | A19 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| EM20 | 24 | FA | E2 | 0-0 | 99-99-99 | D06208J | A20 | \$D | *9 | D00883A | REF | | | ALL | | |
| FK01 | 24 | FA | F2 | 0-0 | SPARE | D06242J | A01 | \$D | *E | GD00085 | S.. | 2 | *2 | ALL | | |
| FK02 | 24 | FA | F2 | 0-0 | 21-52-11 | D06242J | A02 | \$D | *E | TB0237Z | 9 | BJ | | ALL | | |
| FK03 | 24 | FA | F2 | 0-0 | 21-52-11 | D06242J | A03 | \$D | *E | D00881E | H13 | | | ALL | | |
| FK04 | 24 | FA | F2 | 0-0 | 21-52-11 | D06242J | A04 | \$D | *E | GD00091 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| FK04 | 24 | FA | F2 | 0-0 | 21-52-11 | D06242J | A04 | \$D | *E | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 | | |
| FK05 | 24 | FA | F2 | 0-0 | 21-52-11 | D06242J | A05 | \$D | *E | TB0237Z | 17 | BJ | | ALL | | |
| FK06 | 24 | FA | F2 | 0-0 | 21-52-11 | D06242J | A06 | \$D | *E | D00881E | J12 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| FK07 | 24 | FA | F2 | | 0-0 | 21-52-11 | D06242J | A07 | \$D | *E | GD00083 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 |
| FK07 | 24 | FA | F2 | | 0-0 | 21-52-11 | D06242J | A07 | \$D | *E | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 |
| FK08 | 24 | FA | F2 | | 0-0 | 21-52-31 | D06242J | A08 | \$D | *E | D00881A | F06 | | | ALL |
| FK09 | 24 | FA | F2 | | 0-0 | 21-52-31 | D06242J | A09 | \$D | *E | D00881A | F07 | | | ALL |
| FK10 | 24 | FA | F2 | | 0-0 | 21-52-41 | D06242J | A10 | \$D | *E | D00881E | E02 | | | ALL |
| FK11 | 24 | FA | F2 | | 0-0 | 21-52-41 | D06242J | A11 | \$D | *E | GD00089 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 |
| FK11 | 24 | FA | F2 | | 0-0 | 21-52-41 | D06242J | A11 | \$D | *E | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 |
| FK12 | 24 | FA | F2 | | 0-0 | 21-51-11 | D06242J | A12 | \$D | *E | D00881A | D08 | | | ALL |
| FK13 | 24 | FA | F2 | | 0-0 | 21-28-11 | D06242J | A13 | \$D | *E | D00881A | E06 | | | 050-099, 155-199, 277-299 |
| FK13 | 24 | FA | F2 | | 0-0 | 21-51-11 | D06242J | A13 | \$D | *E | D00881A | E06 | | | 150-154, 275-276 |
| FK14 | 24 | FA | F2 | | 0-0 | 21-51-11 | D06242J | A14 | \$D | *E | D00881F | D02 | | | ALL |
| FK15 | 24 | FA | F2 | | 0-0 | 21-43-12 | D06242J | A15 | \$D | *E | D00881D | D03 | | | ALL |
| FK16 | 24 | FA | F2 | | 0-0 | 21-58-11 | D06242J | A16 | \$D | * | D00881E | G03 | | | ALL |
| FK17 | 24 | FA | F2 | | 0-0 | 21-58-11 | D06242J | A17 | \$D | * | D00881F | F03 | | | ALL |
| FK18 | 24 | FA | F2 | | 0-0 | 21-58-14 | D06242J | A18 | \$D | * | D00881A | E11 | | | ALL |
| FK19 | 24 | FA | F2 | | 0-0 | 21-43-12 | D06242J | A19 | \$D | * | D00881D | D02 | | | ALL |
| FK20 | 24 | FA | F2 | | 0-0 | 99-99-99 | D06242J | A20 | \$D | * | D00881A | REF | | | ALL |
| FL01 | 24 | FB | F4 | | 0-0 | SPARE | D06242J | B01 | \$D | * | GD00085 | S.. | 2 | *2 | ALL |
| FL02 | 24 | FB | F4 | | 0-0 | 21-64-11 | D06242J | B02 | \$D | * | GD00091 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 |
| FL02 | 24 | FB | F4 | | 0-0 | 21-64-11 | D06242J | B02 | \$D | * | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 |
| FL03 | 24 | FB | F4 | | 0-0 | 21-64-11 | D06242J | B03 | \$D | * | TB0237X | C014 | BJ | | ALL |
| FL04 | 24 | FB | F4 | | 0-0 | 21-64-11 | D06242J | B04 | \$D | * | TB0237Z | 9 | BJ | | ALL |
| FL05 | 24 | FB | F4 | | 0-0 | 21-64-11 | D06242J | B05 | \$D | * | GD00091 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 |
| FL05 | 24 | FB | F4 | | 0-0 | 21-64-11 | D06242J | B05 | \$D | * | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 |
| FL06 | 24 | FB | F4 | | 0-0 | 21-64-11 | D06242J | B06 | \$D | * | D00881F | G09 | | | ALL |
| FL07 | 24 | FB | F4 | | 0-0 | 21-64-11 | D06242J | B07 | \$D | * | TB0237Z | 9 | BJ | | ALL |
| FL08 | 24 | FB | F4 | | 0-0 | SPARE | D06242J | B08 | \$D | * | D00881A | REF | ** | | ALL |
| FL09 | 24 | FB | F4 | | 0-0 | SPARE | D06242J | B09 | \$D | * | D00881A | REF | ** | | ALL |
| FL10 | 24 | FB | F4 | | 0-0 | SPARE | D06242J | B10 | \$D | * | D00881A | REF | ** | | ALL |
| FL11 | 24 | FB | F4 | | 0-0 | 21-58-15 | D06242J | B11 | \$D | * | D00881A | J13 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 9
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| FL12 | 24 | FB | F4 | 0-0 | 21-51-21 | D06242J | B12 | \$D | * | D00881A | G10 | | | ALL | | |
| FL13 | 24 | FB | F4 | 0-0 | 21-51-21 | D06242J | B13 | \$D | * | D00881A | D05 | | | ALL | | |
| FL14 | 24 | FB | F4 | 0-0 | 36-11-62 | D06242J | B14 | \$D | * | D00881B | J12 | | | ALL | | |
| FL15 | 24 | FB | F4 | 0-0 | 21-26-11 | D06242J | B15 | \$D | * | D00881A | G14 | | | ALL | | |
| FL16 | 24 | FB | F4 | 0-0 | 21-26-11 | D06242J | B16 | \$D | * | D00881A | K14 | | | ALL | | |
| FL17 | 24 | FB | F4 | 0-0 | 21-51-11 | D06242J | B17 | \$D | * | D00881A | E13 | | | 050, 150-154, 275-276 | | |
| FL17 | 24 | FB | F4 | 0-0 | SPARE | D06242J | B17 | \$D | * | D00881A | REF | ** | | 051-099, 155-199, 277-299 | | |
| FL18 | 24 | FB | F4 | 0-0 | 21-51-11 | D06242J | B18 | \$D | * | D00881B | F08 | | | ALL | | |
| FL19 | 24 | FB | F4 | 0-0 | 26-18-22 | D06242J | B19 | \$D | * | D00881D | H05 | | | ALL | | |
| FL20 | 24 | FB | F4 | 0-0 | 99-99-99 | D06242J | B20 | \$D | * | D00881A | REF | | | ALL | | |
| FM01 | 24 | FA | F1 | 0-0 | 99-99-99 | D06242J | A01 | \$D | *E | D00883A | REF | | | ALL | | |
| FM02 | 24 | FA | F1 | 0-0 | SPARE | D06242J | A02 | \$D | *E | D00883A | REF | ** | | ALL | | |
| FM03 | 24 | FA | F1 | 0-0 | SPARE | D06242J | A03 | \$D | *E | D00883A | REF | ** | | ALL | | |
| FM04 | 24 | FA | F1 | 0-0 | SPARE | D06242J | A04 | \$D | *E | D00883A | REF | ** | | ALL | | |
| FM05 | 24 | FA | F1 | 0-0 | SPARE | D06242J | A05 | \$D | *E | D00883A | REF | ** | | ALL | | |
| FM06 | 24 | FA | F1 | 0-0 | SPARE | D06242J | A06 | \$D | *E | D00883A | REF | ** | | ALL | | |
| FM07 | 24 | FA | F1 | 0-0 | SPARE | D06242J | A07 | \$D | *E | D00883A | REF | ** | | ALL | | |
| FM08 | 24 | FA | F1 | 0-0 | SPARE | D06242J | A08 | \$D | *E | D00883A | REF | ** | | ALL | | |
| FM09 | 24 | FA | F1 | 0-0 | SPARE | D06242J | A09 | \$D | *E | D00883A | REF | ** | | ALL | | |
| FM10 | 24 | FA | F1 | 0-0 | SPARE | D06242J | A10 | \$D | *E | D00883A | REF | ** | | ALL | | |
| FM11 | 24 | FA | F1 | 0-0 | SPARE | D06242J | A11 | \$D | *E | D00883A | REF | ** | | ALL | | |
| FM12 | 24 | FA | F1 | 0-0 | 21-51-11 | D06242J | A12 | \$D | *E | D00883A | D08 | | | ALL | | |
| FM13 | 24 | FA | F1 | 0-0 | 21-28-11 | D06242J | A13 | \$D | *E | D00883A | E06 | | | 050-099, 155-199, 277-299 | | |
| FM13 | 24 | FA | F1 | 0-0 | 21-51-11 | D06242J | A13 | \$D | *E | D00883A | E06 | | | 150-154, 275-276 | | |
| FM14 | 24 | FA | F1 | 0-0 | 21-51-11 | D06242J | A14 | \$D | *E | D00883F | D02 | | | ALL | | |
| FM15 | 24 | FA | F1 | 0-0 | SPARE | D06242J | A15 | \$D | *E | D00883A | REF | ** | | ALL | | |
| FM16 | 24 | FA | F1 | 0-0 | 21-58-11 | D06242J | A16 | \$D | * | D00883E | G03 | | | ALL | | |
| FM17 | 24 | FA | F1 | 0-0 | 21-58-11 | D06242J | A17 | \$D | * | D00883F | F03 | | | ALL | | |
| FM18 | 24 | FA | F1 | 0-0 | 21-58-14 | D06242J | A18 | \$D | * | D00883A | E11 | | | ALL | | |
| FM19 | 24 | FA | F1 | 0-0 | SPARE | D06242J | A19 | \$D | * | D00883A | REF | ** | | ALL | | |
| FM20 | 24 | FA | F1 | 0-0 | 99-99-99 | D06242J | A20 | \$D | * | D00883A | REF | | | ALL | | |
| FN01 | 24 | FB | F3 | 0-0 | 99-99-99 | D06242J | B01 | \$D | * | D00883A | REF | | | ALL | | |
| FN02 | 24 | FB | F3 | 0-0 | SPARE | D06242J | B02 | \$D | * | D00883A | REF | ** | | ALL | | |
| FN03 | 24 | FB | F3 | 0-0 | SPARE | D06242J | B03 | \$D | * | D00883A | REF | ** | | ALL | | |
| FN04 | 24 | FB | F3 | 0-0 | SPARE | D06242J | B04 | \$D | * | D00883A | REF | ** | | ALL | | |
| FN05 | 24 | FB | F3 | 0-0 | SPARE | D06242J | B05 | \$D | * | D00883A | REF | ** | | ALL | | |
| FN06 | 24 | FB | F3 | 0-0 | SPARE | D06242J | B06 | \$D | * | D00883A | REF | ** | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 10

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| FN07 | 24 | FB | F3 | | 0-0 | SPARE | D06242J | B07 | \$D | * | D00883A | REF | ** | | ALL |
| FN08 | 24 | FB | F3 | | 0-0 | 21-64-11 | D06242J | B08 | \$D | * | GD00169 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 |
| FN08 | 24 | FB | F3 | | 0-0 | 21-64-11 | D06242J | B08 | \$D | * | GDX0001 | D.. | 2 | | 155-157, 165-199, 277-299 |
| FN09 | 24 | FB | F3 | | 0-0 | 21-64-11 | D06242J | B09 | \$D | * | D00883F | B09 | | | ALL |
| FN10 | 24 | FB | F3 | | 0-0 | 21-64-11 | D06242J | B10 | \$D | * | TB0237Z | 10 | BJ | | ALL |
| FN11 | 24 | FB | F3 | | 0-0 | 21-58-15 | D06242J | B11 | \$D | * | D00883A | J13 | | | ALL |
| FN12 | 24 | FB | F3 | | 0-0 | 21-51-21 | D06242J | B12 | \$D | * | D00883A | G10 | | | ALL |
| FN13 | 24 | FB | F3 | | 0-0 | 21-51-21 | D06242J | B13 | \$D | * | D00883A | D05 | | | ALL |
| FN14 | 24 | FB | F3 | | 0-0 | 36-11-62 | D06242J | B14 | \$D | * | D00883B | J12 | | | ALL |
| FN15 | 24 | FB | F3 | | 0-0 | 21-26-11 | D06242J | B15 | \$D | * | D00883A | G14 | | | ALL |
| FN16 | 24 | FB | F3 | | 0-0 | 21-26-11 | D06242J | B16 | \$D | * | D00883A | K14 | | | ALL |
| FN17 | 24 | FB | F3 | | 0-0 | 21-51-11 | D06242J | B17 | \$D | * | D00883A | E13 | | | 050, 150-154, 275-276 |
| FN17 | 24 | FB | F3 | | 0-0 | SPARE | D06242J | B17 | \$D | * | D00883A | REF | ** | | 051-099, 155-199, 277-299 |
| FN18 | 24 | FB | F3 | | 0-0 | 21-51-11 | D06242J | B18 | \$D | * | D00883B | F08 | | | ALL |
| FN19 | 24 | FB | F3 | | 0-0 | 26-18-22 | D06242J | B19 | \$D | * | D00883D | H05 | | | ALL |
| FN20 | 24 | FB | F3 | | 0-0 | 99-99-99 | D06242J | B20 | \$D | * | GD00155 | REF | | | 050-099, 150-154, 275-276 |
| FN20 | 24 | FB | F3 | | 0-0 | 99-99-99 | D06242J | B20 | \$D | * | D00883A | REF | | | 155-199, 277-299 |
| GK01 | 24 | FA | G1 | | 0-0 | 99-99-99 | D06202J | A01 | \$D | *C | D00881A | REF | | | ALL |
| GK02 | 24 | FA | G1 | | 0-0 | 21-25-11 | D06202J | A02 | \$D | *C | D00881A | E07 | | | ALL |
| GK03 | 24 | FA | G1 | | 0-0 | SPARE | D06202J | A03 | \$D | *C | D00881A | REF | ** | | ALL |
| GK04 | 24 | FA | G1 | | 0-0 | 27-18-11 | D06202J | A04 | \$D | *C | D00881E | H02 | | | 050-099, 150-154, 162-165, 275-276 |
| GK04 | 24 | FA | G1 | | 0-0 | SPARE | D06202J | A04 | \$D | *C | D00881A | REF | ** | | 155-157, 166-199, 277-299 |
| GK05 | 24 | FA | G1 | | 0-0 | 27-13-11 | D06202J | A05 | \$D | *C | D00881B | K13 | | | ALL |
| GK06 | 24 | FA | G1 | | 0-0 | 30-21-11 | D06202J | A06 | \$D | *C | D00881E | D09 | | | ALL |
| GK07 | 24 | FA | G1 | | 0-0 | 27-18-11 | D06202J | A07 | \$D | *C | D00881E | H04 | | | 050-099, 150-154, 162-165, 275-276 |
| GK07 | 24 | FA | G1 | | 0-0 | SPARE | D06202J | A07 | \$D | *C | D00881A | REF | ** | | 155-157, 166-199, 277-299 |
| GK08 | 24 | FA | G1 | | 0-0 | SPARE | D06202J | A08 | \$D | *C | D00881A | REF | ** | | 050-099, 162-199, 275-299 |
| GK08 | 24 | FA | G1 | | 0-0 | SPARE | D06202J | A08 | \$D | *C | GD00083 | A.. | 2 | | 150-154 |
| GK08 | 24 | FA | G1 | | 0-0 | SPARE | D06202J | A08 | \$D | *C | GDX0002 | A.. | 2 | | 155-157 |
| GK09 | 24 | FA | G1 | | 0-0 | 21-58-16 | D06202J | A09 | \$D | *C | D00881D | E15 | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 11
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|---------------------------------------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| GK10 | 24 | FA | G1 | 0-0 | 29-31-11 | D06202J | A10 | \$D | *C | GD00091 | A.. | 2 | 050-099, 150-154, 162-164, 275-276 | | | |
| GK10 | 24 | FA | G1 | 0-0 | 29-31-11 | D06202J | A10 | \$D | *C | GDX0002 | A.. | 2 | 155-157, 165-199, 277-299 | | | |
| GK11 | 24 | FA | G1 | 0-0 | 28-42-11 | D06202J | A11 | \$D | *C | D00881D | H08 | | ALL | | | |
| GK12 | 24 | FA | G1 | 0-0 | 29-31-11 | D06202J | A12 | \$D | *C | D00881B | H03 | | ALL | | | |
| GK13 | 24 | FA | G1 | 0-0 | 24-11-11 | D06202J | A13 | \$D | *C | D00881F | D07 | | ALL | | | |
| GK14 | 24 | FA | G1 | 0-0 | 27-23-11 | D06202J | A14 | \$D | *C | D00881A | H08 | | ALL | | | |
| GK15 | 24 | FA | G1 | 0-0 | 78-36-11 | D06202J | A15 | \$D | *C | D00881B | J10 | | ALL | | | |
| GK16 | 24 | FA | G1 | 0-0 | 30-21-11 | D06202J | A16 | \$D | *C | D00881F | G05 | | 050-099, 150-154, 275-276 | | | |
| GK16 | 24 | FA | G1 | 0-0 | 30-21-11 | D06202J | A16 | \$D | * | D00881F | G05 | | 155-199, 277-299 | | | |
| GK17 | 24 | FA | G1 | 0-0 | 29-32-11 | D06202J | A17 | \$D | *C | D00881B | J04 | | 050-099, 150-154, 275-276 | | | |
| GK17 | 24 | FA | G1 | 0-0 | 29-32-11 | D06202J | A17 | \$D | * | D00881B | J04 | | 155-199, 277-299 | | | |
| GK18 | 24 | FA | G1 | 0-0 | 29-32-11 | D06202J | A18 | \$D | *C | D00881B | J05 | | 050-099, 150-154, 275-276 | | | |
| GK18 | 24 | FA | G1 | 0-0 | 29-32-11 | D06202J | A18 | \$D | * | D00881B | J05 | | 155-199, 277-299 | | | |
| GK19 | 24 | FA | G1 | 0-0 | 79-35-11 | D06202J | A19 | \$D | *C | D00881A | H04 | | 050-099, 150-154, 275-276 | | | |
| GK19 | 24 | FA | G1 | 0-0 | 79-35-11 | D06202J | A19 | \$D | * | D00881A | H04 | | 155-199, 277-299 | | | |
| GK20 | 24 | FA | G1 | 0-0 | 99-99-99 | D06202J | A20 | \$D | *C | D00881A | REF | | 050-099, 150-154, 275-276 | | | |
| GK20 | 24 | FA | G1 | 0-0 | 99-99-99 | D06202J | A20 | \$D | * | D00881A | REF | | 155-199, 277-299 | | | |
| GL01 | 24 | FB | G3 | 0-0 | 99-99-99 | D06202J | B01 | \$D | *C | D00881A | REF | | 050-099, 150-154, 275-276 | | | |
| GL01 | 24 | FB | G3 | 0-0 | 99-99-99 | D06202J | B01 | \$D | * | D00881A | REF | | 155-199, 277-299 | | | |
| GL02 | 24 | FB | G3 | 0-0 | 73-21-14 | D06202J | B02 | \$D | *C | D00881B | A14 | | 050-099, 150-154, 275-276 | | | |
| GL02 | 24 | FB | G3 | 0-0 | 73-21-14 | D06202J | B02 | \$D | * | D00881B | A14 | | 155-199, 277-299 | | | |
| GL03 | 24 | FB | G3 | 0-0 | 73-21-14 | D06202J | B03 | \$D | *C | D00881B | B14 | | 050-099, 150-154, 275-276 | | | |
| GL03 | 24 | FB | G3 | 0-0 | 73-21-14 | D06202J | B03 | \$D | * | D00881B | B14 | | 155-199, 277-299 | | | |
| GL04 | 24 | FB | G3 | 0-0 | 73-21-14 | D06202J | B04 | \$D | *C | GD00091 | S.. | 2 | 050-099, 150-154, 275-276 | | | |
| GL04 | 24 | FB | G3 | 0-0 | 73-21-14 | D06202J | B04 | \$D | * | GDX0002 | S.. | 2 | 155-157, 165-199, 277-299 | | | |
| GL04 | 24 | FB | G3 | 0-0 | 73-21-14 | D06202J | B04 | \$D | * | GD00091 | S.. | 2 | 162-164 | | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 12

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| GL05 | 24 | FB | G3 | | 0-0 | 75-23-11 | D06202J | B05 | \$D | *C | D00881B | H05 | | | 050-099, 150-154, 275-276 |
| GL05 | 24 | FB | G3 | | 0-0 | 75-23-11 | D06202J | B05 | \$D | * | D00881B | H05 | | | 155-199, 277-299 |
| GL06 | 24 | FB | G3 | | 0-0 | 21-44-22 | D06202J | B06 | \$D | *C | D00881D | D10 | | | 050-099, 150-154 |
| GL06 | 24 | FB | G3 | | 0-0 | 21-44-22 | D06202J | B06 | \$D | * | D00881D | D10 | | | 155-199 |
| GL06 | 24 | FB | G3 | | 0-0 | SPARE | D06202J | B06 | \$D | *C | D00881A | REF | ** | | 275-276 |
| GL06 | 24 | FB | G3 | | 0-0 | SPARE | D06202J | B06 | \$D | * | D00881A | REF | ** | | 277-299 |
| GL07 | 24 | FB | G3 | | 0-0 | 21-44-22 | D06202J | B07 | \$D | *C | D00881D | D09 | | | 050-099, 150-154 |
| GL07 | 24 | FB | G3 | | 0-0 | 21-44-22 | D06202J | B07 | \$D | * | D00881D | D09 | | | 155-199 |
| GL07 | 24 | FB | G3 | | 0-0 | SPARE | D06202J | B07 | \$D | *C | D00881A | REF | ** | | 275-276 |
| GL07 | 24 | FB | G3 | | 0-0 | SPARE | D06202J | B07 | \$D | * | D00881A | REF | ** | | 277-299 |
| GL08 | 24 | FB | G3 | | 0-0 | 30-21-11 | D06202J | B08 | \$D | *C | D00881B | H12 | | | 050-099, 150-154 |
| GL08 | 24 | FB | G3 | | 0-0 | 30-21-11 | D06202J | B08 | \$D | * | D00881B | H12 | | | 155-199 |
| GL08 | 24 | FB | G3 | | 0-0 | SPARE | D06202J | B08 | \$D | *C | D00881A | REF | ** | | 275-276 |
| GL08 | 24 | FB | G3 | | 0-0 | SPARE | D06202J | B08 | \$D | * | D00881A | REF | ** | | 277-299 |
| GL09 | 24 | FB | G3 | | 0-0 | SPARE | D06202J | B09 | \$D | *C | D00881A | REF | ** | | 050-099, 150-154, 275-276 |
| GL09 | 24 | FB | G3 | | 0-0 | SPARE | D06202J | B09 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 |
| GL10 | 24 | FB | G3 | | 0-0 | 79-31-11 | D06202J | B10 | \$D | *C | D00881B | J08 | | | 050-099, 150-154, 275-276 |
| GL10 | 24 | FB | G3 | | 0-0 | 79-31-11 | D06202J | B10 | \$D | * | D00881B | J08 | | | 155-199, 277-299 |
| GL11 | 24 | FB | G3 | | 0-0 | 79-31-11 | D06202J | B11 | \$D | *C | GD00091 | D.. | 2 | | 050-099, 150-154, 275-276 |
| GL11 | 24 | FB | G3 | | 0-0 | 79-31-11 | D06202J | B11 | \$D | * | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 |
| GL11 | 24 | FB | G3 | | 0-0 | 79-31-11 | D06202J | B11 | \$D | * | GD00091 | D.. | 2 | | 162-164 |
| GL12 | 24 | FB | G3 | | 0-0 | 79-31-11 | D06202J | B12 | \$D | *C | TB0237Z | 9 | BJ | | 050-099, 150-154, 275-276 |
| GL12 | 24 | FB | G3 | | 0-0 | 79-31-11 | D06202J | B12 | \$D | * | TB0237Z | 9 | BJ | | 155-199, 277-299 |
| GL13 | 24 | FB | G3 | | 0-0 | 32-09-11 | D06202J | B13 | \$D | *C | D00881F | E09 | | | 050-099, 150-154, 275-276 |
| GL13 | 24 | FB | G3 | | 0-0 | 32-09-11 | D06202J | B13 | \$D | * | D00881F | E09 | | | 155-199, 277-299 |
| GL14 | 24 | FB | G3 | | 0-0 | 32-09-11 | D06202J | B14 | \$D | *C | D00881F | F08 | | | 050-099, 150-154, 275-276 |
| GL14 | 24 | FB | G3 | | 0-0 | 32-09-11 | D06202J | B14 | \$D | * | D00881F | F08 | | | 155-199, 277-299 |
| GL15 | 24 | FB | G3 | | 0-0 | 27-28-11 | D06202J | B15 | \$D | *C | D00881E | H10 | | | 050-099, 150-154, 275-276 |
| GL15 | 24 | FB | G3 | | 0-0 | 27-28-11 | D06202J | B15 | \$D | * | D00881E | H10 | | | 155-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 13
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------------------------------------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| GL16 | 24 | FB | G3 | 0-0 | 27-28-11 | D06202J | B16 | \$D | *C | GD00089 | A.. | 2 | 050-099, 150-154, 275-276 | | |
| GL16 | 24 | FB | G3 | 0-0 | 27-28-11 | D06202J | B16 | \$D | * | GDX0002 | A.. | 2 | 155-157, 165-199, 277-299 | | |
| GL16 | 24 | FB | G3 | 0-0 | 27-28-11 | D06202J | B16 | \$D | * | GD00089 | A.. | 2 | 162-164 | | |
| GL17 | 24 | FB | G3 | 0-0 | 21-43-11 | D06202J | B17 | \$D | *C | D00881E | D10 | | 050-099, 150-154, 275-276 | | |
| GL17 | 24 | FB | G3 | 0-0 | 21-43-11 | D06202J | B17 | \$D | * | D00881E | D10 | | 155-199, 277-299 | | |
| GL18 | 24 | FB | G3 | 0-0 | 21-44-11 | D06202J | B18 | \$D | *C | D00881E | D12 | | 050-099, 150-154, 275-276 | | |
| GL18 | 24 | FB | G3 | 0-0 | 21-44-11 | D06202J | B18 | \$D | * | D00881E | D12 | | 155-199, 277-299 | | |
| GL19 | 24 | FB | G3 | 0-0 | 27-31-11 | D06202J | B19 | \$D | *C | D00881D | C04 | | 050-099, 150-154, 275-276 | | |
| GL19 | 24 | FB | G3 | 0-0 | 27-31-11 | D06202J | B19 | \$D | * | D00881D | C04 | | 155-199, 277-299 | | |
| GL20 | 24 | FB | G3 | 0-0 | 99-99-99 | D06202J | B20 | \$D | *C | D00881A | REF | | 050-099, 150-154, 275-276 | | |
| GL20 | 24 | FB | G3 | 0-0 | 99-99-99 | D06202J | B20 | \$D | * | D00881A | REF | | 155-199, 277-299 | | |
| GM01 | 24 | FA | G2 | 0-0 | SPARE | D06202J | A01 | \$D | *C | GD00155 | S.. | 2 | ALL | | |
| GM02 | 24 | FA | G2 | 0-0 | 21-25-11 | D06202J | A02 | \$D | *C | D00883A | E07 | | ALL | | |
| GM03 | 24 | FA | G2 | 0-0 | 27-18-11 | D06202J | A03 | \$D | *C | GD00169 | A.. | 2 | 050-099, 150-154, 162-164, 275-276 | | |
| GM03 | 24 | FA | G2 | 0-0 | SPARE | D06202J | A03 | \$D | *C | GDX0001 | A.. | 2 | 155-157, 166-199, 277-299 | | |
| GM03 | 24 | FA | G2 | 0-0 | 27-18-11 | D06202J | A03 | \$D | *C | GDX0001 | A.. | 2 | 165 | | |
| GM04 | 24 | FA | G2 | 0-0 | 27-18-11 | D06202J | A04 | \$D | *C | D00883E | H02 | | 050-099, 150-154, 162-165, 275-276 | | |
| GM04 | 24 | FA | G2 | 0-0 | SPARE | D06202J | A04 | \$D | *C | D00883A | REF | ** | 155-157, 166-199, 277-299 | | |
| GM05 | 24 | FA | G2 | 0-0 | 27-13-11 | D06202J | A05 | \$D | *C | D00883B | K13 | | ALL | | |
| GM06 | 24 | FA | G2 | 0-0 | 30-21-11 | D06202J | A06 | \$D | *C | D00883E | D09 | | ALL | | |
| GM07 | 24 | FA | G2 | 0-0 | 27-18-11 | D06202J | A07 | \$D | *C | D00883E | H04 | | 050-099, 150-154, 162-165, 275-276 | | |
| GM07 | 24 | FA | G2 | 0-0 | SPARE | D06202J | A07 | \$D | *C | D00883A | REF | ** | 155-157, 166-199, 277-299 | | |
| GM08 | 24 | FA | G2 | 0-0 | 27-18-11 | D06202J | A08 | \$D | *C | GD00169 | A.. | 2 | 050-099, 150-154, 162-164, 275-276 | | |
| GM08 | 24 | FA | G2 | 0-0 | 27-18-11 | D06202J | A08 | \$D | *C | GDX0001 | A.. | 2 | 155-156, 165-166 | | |
| GM08 | 24 | FA | G2 | 0-0 | SPARE | D06202J | A08 | \$D | *C | GDX0001 | A.. | 2 | 157, 167-199, 277-299 | | |
| GM09 | 24 | FA | G2 | 0-0 | 21-58-16 | D06202J | A09 | \$D | *C | D00883D | E15 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 14

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| GM10 | 24 | FA | G2 | 0-0 | SPARE | D06202J | A10 | \$D | *C | D00883A | REF | ** | | ALL | | |
| GM11 | 24 | FA | G2 | 0-0 | 28-42-11 | D06202J | A11 | \$D | *C | D00883D | H08 | | | ALL | | |
| GM12 | 24 | FA | G2 | 0-0 | 29-31-11 | D06202J | A12 | \$D | *C | D00883B | H03 | | | ALL | | |
| GM13 | 24 | FA | G2 | 0-0 | 24-11-11 | D06202J | A13 | \$D | *C | D00883F | D07 | | | ALL | | |
| GM14 | 24 | FA | G2 | 0-0 | 27-23-11 | D06202J | A14 | \$D | *C | D00883A | H08 | | | ALL | | |
| GM15 | 24 | FA | G2 | 0-0 | 78-36-11 | D06202J | A15 | \$D | *C | D00883B | J10 | | | ALL | | |
| GM16 | 24 | FA | G2 | 0-0 | 30-21-11 | D06202J | A16 | \$D | *C | D00883F | G05 | | | 050-099, 150-154, 275-276 | | |
| GM16 | 24 | FA | G2 | 0-0 | 30-21-11 | D06202J | A16 | \$D | * | D00883F | G05 | | | 155-199, 277-299 | | |
| GM17 | 24 | FA | G2 | 0-0 | SPARE | D06202J | A17 | \$D | *C | D00883A | REF | ** | | 050-099, 150-154, 275-276 | | |
| GM17 | 24 | FA | G2 | 0-0 | SPARE | D06202J | A17 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | | |
| GM18 | 24 | FA | G2 | 0-0 | SPARE | D06202J | A18 | \$D | *C | D00883A | REF | ** | | 050-099, 150-154, 275-276 | | |
| GM18 | 24 | FA | G2 | 0-0 | SPARE | D06202J | A18 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | | |
| GM19 | 24 | FA | G2 | 0-0 | 79-35-11 | D06202J | A19 | \$D | *C | D00883A | H04 | | | 050-099, 150-154, 275-276 | | |
| GM19 | 24 | FA | G2 | 0-0 | 79-35-11 | D06202J | A19 | \$D | * | D00883A | H04 | | | 155-199, 277-299 | | |
| GM20 | 24 | FA | G2 | 0-0 | 99-99-99 | D06202J | A20 | \$D | *C | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| GM20 | 24 | FA | G2 | 0-0 | 99-99-99 | D06202J | A20 | \$D | * | D00883A | REF | | | 155-199, 277-299 | | |
| GN01 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B01 | \$D | *C | GD00155 | S.. | 2 | | 050-099, 150-154, 275-276 | | |
| GN01 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B01 | \$D | * | GD00155 | S.. | 2 | | 155-199, 277-299 | | |
| GN02 | 24 | FB | G4 | 0-0 | 73-21-14 | D06202J | B02 | \$D | *C | D00883B | A14 | | | 050-099, 150-154, 275-276 | | |
| GN02 | 24 | FB | G4 | 0-0 | 73-21-14 | D06202J | B02 | \$D | * | D00883B | A14 | | | 155-199, 277-299 | | |
| GN03 | 24 | FB | G4 | 0-0 | 73-21-14 | D06202J | B03 | \$D | *C | D00883B | B14 | | | 050-099, 150-154, 275-276 | | |
| GN03 | 24 | FB | G4 | 0-0 | 73-21-14 | D06202J | B03 | \$D | * | D00883B | B14 | | | 155-199, 277-299 | | |
| GN04 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B04 | \$D | *C | D00883A | REF | ** | | 050-099, 150-154, 275-276 | | |
| GN04 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B04 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | | |
| GN05 | 24 | FB | G4 | 0-0 | 75-23-11 | D06202J | B05 | \$D | *C | D00883B | H05 | | | 050-099, 150-154, 275-276 | | |
| GN05 | 24 | FB | G4 | 0-0 | 75-23-11 | D06202J | B05 | \$D | * | D00883B | H05 | | | 155-199, 277-299 | | |
| GN06 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B06 | \$D | *C | D00883A | REF | ** | | 050-099, 150-154, 275-276 | | |
| GN06 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B06 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 15
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|---------------------------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| GN07 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B07 | \$D | *C | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| GN07 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B07 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| GN08 | 24 | FB | G4 | 0-0 | 30-21-11 | D06202J | B08 | \$D | *C | D00883B | H12 | | 050-099, 150-154 | | |
| GN08 | 24 | FB | G4 | 0-0 | 30-21-11 | D06202J | B08 | \$D | * | D00883B | H12 | | 155-199 | | |
| GN08 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B08 | \$D | *C | D00883A | REF | ** | 275-276 | | |
| GN08 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B08 | \$D | * | D00883A | REF | ** | 277-299 | | |
| GN09 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B09 | \$D | *C | D00883A | REF | ** | 050-099, 275-276 | | |
| GN09 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B09 | \$D | *C | GD00083 | A.. | 2 | 150-154 | | |
| GN09 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B09 | \$D | * | GD00002 | A.. | 2 | 155-157 | | |
| GN09 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B09 | \$D | * | D00883A | REF | ** | 162-199, 277-299 | | |
| GN10 | 24 | FB | G4 | 0-0 | 79-31-11 | D06202J | B10 | \$D | *C | D00883B | J08 | | 050-099, 150-154, 275-276 | | |
| GN10 | 24 | FB | G4 | 0-0 | 79-31-11 | D06202J | B10 | \$D | * | D00883B | J08 | | 155-199, 277-299 | | |
| GN11 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B11 | \$D | *C | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| GN11 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B11 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| GN12 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B12 | \$D | *C | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| GN12 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B12 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| GN13 | 24 | FB | G4 | 0-0 | 32-09-11 | D06202J | B13 | \$D | *C | D00883F | E09 | | 050-099, 150-154, 275-276 | | |
| GN13 | 24 | FB | G4 | 0-0 | 32-09-11 | D06202J | B13 | \$D | * | D00883F | E09 | | 155-199, 277-299 | | |
| GN14 | 24 | FB | G4 | 0-0 | 32-09-11 | D06202J | B14 | \$D | *C | D00883F | F08 | | 050-099, 150-154, 275-276 | | |
| GN14 | 24 | FB | G4 | 0-0 | 32-09-11 | D06202J | B14 | \$D | * | D00883F | F08 | | 155-199, 277-299 | | |
| GN15 | 24 | FB | G4 | 0-0 | 27-28-11 | D06202J | B15 | \$D | *C | D00883E | H10 | | 050-099, 150-154, 275-276 | | |
| GN15 | 24 | FB | G4 | 0-0 | 27-28-11 | D06202J | B15 | \$D | * | D00883E | H10 | | 155-199, 277-299 | | |
| GN16 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B16 | \$D | *C | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| GN16 | 24 | FB | G4 | 0-0 | SPARE | D06202J | B16 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| GN17 | 24 | FB | G4 | 0-0 | 21-43-11 | D06202J | B17 | \$D | *C | D00883E | D10 | | 050-099, 150-154, 275-276 | | |
| GN17 | 24 | FB | G4 | 0-0 | 21-43-11 | D06202J | B17 | \$D | * | D00883E | D10 | | 155-199, 277-299 | | |
| GN18 | 24 | FB | G4 | 0-0 | 21-44-11 | D06202J | B18 | \$D | *C | D00883E | D12 | | 050-099, 150-154, 275-276 | | |
| GN18 | 24 | FB | G4 | 0-0 | 21-44-11 | D06202J | B18 | \$D | * | D00883E | D12 | | 155-199, 277-299 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 16

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| GN19 | 24 | FB | G4 | | 0-0 | 27-31-11 | D06202J | B19 | \$D | *C | D00883D | C04 | | | 050-099, 150-154, 275-276 |
| GN19 | 24 | FB | G4 | | 0-0 | 27-31-11 | D06202J | B19 | \$D | * | D00883D | C04 | | | 155-199, 277-299 |
| GN20 | 24 | FB | G4 | | 0-0 | 99-99-99 | D06202J | B20 | \$D | *C | D00883A | REF | | | 050-099, 150-154, 275-276 |
| GN20 | 24 | FB | G4 | | 0-0 | 99-99-99 | D06202J | B20 | \$D | * | D00883A | REF | | | 155-199, 277-299 |
| HK01 | 24 | FA | H2 | | 0-0 | SPARE | D06232J | A01 | \$D | *G | GD00085 | S.. | 2 | | ALL |
| HK02 | 24 | FA | H2 | | 0-0 | 24-11-11 | D06232J | A02 | \$D | *G | D00881D | A10 | | | ALL |
| HK03 | 24 | FA | H2 | | 0-0 | 24-11-11 | D06232J | A03 | \$D | *G | D00881E | E07 | | | ALL |
| HK04 | 24 | FA | H2 | | 0-0 | 24-28-11 | D06232J | A04 | \$D | *G | D00881E | G09 | | | ALL |
| HK05 | 24 | FA | H2 | | 0-0 | 24-28-21 | D06232J | A05 | \$D | *G | D00881E | E09 | | | ALL |
| HK06 | 24 | FA | H2 | | 0-0 | 30-41-11 | D06232J | A06 | \$D | *G | D00881E | C06 | | | ALL |
| HK07 | 24 | FA | H2 | | 0-0 | 30-41-11 | D06232J | A07 | \$D | *G | D00881A | D02 | | | ALL |
| HK08 | 24 | FA | H2 | | 0-0 | 24-27-11 | D06232J | A08 | \$D | *G | D00881D | B01 | | | ALL |
| HK09 | 24 | FA | H2 | | 0-0 | 24-27-11 | D06232J | A09 | \$D | *G | D00881D | B03 | | | ALL |
| HK10 | 24 | FA | H2 | | 0-0 | 24-27-11 | D06232J | A10 | \$D | *G | D00881D | C06 | | | ALL |
| HK11 | 24 | FA | H2 | | 0-0 | 24-11-11 | D06232J | A11 | \$D | *G | TB0237Z | 9 | BJ | | ALL |
| HK12 | 24 | FA | H2 | | 0-0 | 24-11-11 | D06232J | A12 | \$D | *G | D00881F | G01 | | | ALL |
| HK13 | 24 | FA | H2 | | 0-0 | SPARE | D06232J | A13 | \$D | *G | D00881A | REF | ** | | ALL |
| HK14 | 24 | FA | H2 | | 0-0 | SPARE | D06232J | A14 | \$D | *G | D00881A | REF | ** | | ALL |
| HK15 | 24 | FA | H2 | | 0-0 | SPARE | D06232J | A15 | \$D | *G | D00881A | REF | ** | | ALL |
| HK16 | 24 | FA | H2 | | 0-0 | SPARE | D06232J | A16 | \$D | * | D00881A | REF | ** | | ALL |
| HK17 | 24 | FA | H2 | | 0-0 | SPARE | D06232J | A17 | \$D | * | D00881A | REF | ** | | ALL |
| HK18 | 24 | FA | H2 | | 0-0 | SPARE | D06232J | A18 | \$D | * | D00881A | REF | ** | | ALL |
| HK19 | 24 | FA | H2 | | 0-0 | SPARE | D06232J | A19 | \$D | * | D00881A | REF | ** | | ALL |
| HK20 | 24 | FA | H2 | | 0-0 | 99-99-99 | D06232J | A20 | \$D | * | D00881A | REF | | | ALL |
| HM01 | 24 | FA | H1 | | 0-0 | 99-99-99 | D06232J | A01 | \$D | *G | D00883A | REF | | | ALL |
| HM02 | 24 | FA | H1 | | 0-0 | 24-11-11 | D06232J | A02 | \$D | *G | D00883D | A10 | | | ALL |
| HM03 | 24 | FA | H1 | | 0-0 | 24-11-11 | D06232J | A03 | \$D | *G | D00883E | E07 | | | ALL |
| HM04 | 24 | FA | H1 | | 0-0 | 24-28-11 | D06232J | A04 | \$D | *G | D00883E | G09 | | | ALL |
| HM05 | 24 | FA | H1 | | 0-0 | 24-28-21 | D06232J | A05 | \$D | *G | D00883E | E09 | | | ALL |
| HM06 | 24 | FA | H1 | | 0-0 | 30-41-11 | D06232J | A06 | \$D | *G | D00883E | C06 | | | ALL |
| HM07 | 24 | FA | H1 | | 0-0 | 30-41-11 | D06232J | A07 | \$D | *G | D00883A | D02 | | | ALL |
| HM08 | 24 | FA | H1 | | 0-0 | 24-27-11 | D06232J | A08 | \$D | *G | D00883D | B01 | | | ALL |
| HM09 | 24 | FA | H1 | | 0-0 | 24-27-11 | D06232J | A09 | \$D | *G | D00883D | B03 | | | ALL |
| HM10 | 24 | FA | H1 | | 0-0 | 24-27-11 | D06232J | A10 | \$D | *G | D00883D | C06 | | | ALL |
| HM11 | 24 | FA | H1 | | 0-0 | SPARE | D06232J | A11 | \$D | *G | D00883A | REF | ** | | ALL |
| HM12 | 24 | FA | H1 | | 0-0 | 24-11-11 | D06232J | A12 | \$D | *G | D00883F | G01 | | | ALL |
| HM13 | 24 | FA | H1 | | 0-0 | SPARE | D06232J | A13 | \$D | *G | D00883A | REF | ** | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W2000
 Page 17
 Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| HM14 | 24 | FA | H1 | 0-0 | SPARE | D06232J | A14 | \$D | *G | D00883A | REF | ** | | ALL | | |
| HM15 | 24 | FA | H1 | 0-0 | SPARE | D06232J | A15 | \$D | *G | D00883A | REF | ** | | ALL | | |
| HM16 | 24 | FA | H1 | 0-0 | SPARE | D06232J | A16 | \$D | * | D00883A | REF | ** | | ALL | | |
| HM17 | 24 | FA | H1 | 0-0 | SPARE | D06232J | A17 | \$D | * | D00883A | REF | ** | | ALL | | |
| HM18 | 24 | FA | H1 | 0-0 | SPARE | D06232J | A18 | \$D | * | D00883A | REF | ** | | ALL | | |
| HM19 | 24 | FA | H1 | 0-0 | SPARE | D06232J | A19 | \$D | * | D00883A | REF | ** | | ALL | | |
| HM20 | 24 | FA | H1 | 0-0 | 99-99-99 | D06232J | A20 | \$D | * | GD00155 | REF | | | 050-099, 150-154, 275-276 | | |
| HM20 | 24 | FA | H1 | 0-0 | 99-99-99 | D06232J | A20 | \$D | * | D00883A | REF | | | 155-199, 277-299 | | |
| LK01 | 24 | FA | L1 | 0-0 | 99-99-99 | D06214J | A01 | \$D | *2 | D00881A | REF | | | ALL | | |
| LK02 | 24 | FA | L1 | 0-0 | 29-32-11 | D06214J | A02 | \$D | *2 | D00881A | K04 | | | ALL | | |
| LK03 | 24 | FA | L1 | 0-0 | SPARE | D06214J | A03 | \$D | *2 | D00881A | REF | ** | | 050-099, 275-299 | | |
| LK03 | 24 | FA | L1 | 0-0 | SPARE | D06214J | A03 | \$D | *2 | D00881D | J02 | | | 150-199 | | |
| LK04 | 24 | FA | L1 | 0-0 | SPARE | D06214J | A04 | \$D | *2 | D00881A | REF | ** | | ALL | | |
| LK05 | 24 | FA | L1 | 0-0 | SPARE | D06214J | A05 | \$D | *2 | D00881B | K14 | | | 050-099, 150-199 | | |
| LK05 | 24 | FA | L1 | 0-0 | 30-21-11 | D06214J | A05 | \$D | *2 | D00881E | G15 | | | 275-299 | | |
| LK06 | 24 | FA | L1 | 0-0 | 28-22-21 | D06214J | A06 | \$D | *2 | D00881E | C01 | | | ALL | | |
| LK07 | 24 | FA | L1 | 0-0 | SPARE | D06214J | A07 | \$D | *2 | D00881A | REF | ** | | ALL | | |
| LK08 | 24 | FA | L1 | 0-0 | 73-33-11 | D06214J | A08 | \$D | *2 | D00881D | G14 | | | ALL | | |
| LK09 | 24 | FA | L1 | 0-0 | SPARE | D06214J | A09 | \$D | *2 | D00881A | REF | ** | | ALL | | |
| LK10 | 24 | FA | L1 | 0-0 | SPARE | D06214J | A10 | \$D | *2 | D00881A | REF | ** | | ALL | | |
| LK11 | 24 | FA | L1 | 0-0 | 79-33-11 | D06214J | A11 | \$D | *2 | D00881D | K10 | | | ALL | | |
| LK12 | 24 | FA | L1 | 0-0 | 30-21-11 | D06214J | A12 | \$D | *2 | D00881E | G15 | | | 050-099, 150-199 | | |
| LK12 | 24 | FA | L1 | 0-0 | SPARE | D06214J | A12 | \$D | *2 | D00881A | REF | ** | | 275-299 | | |
| LK13 | 24 | FA | L1 | 0-0 | SPARE | D06214J | A13 | \$D | *2 | D00881A | REF | ** | | ALL | | |
| LK14 | 24 | FA | L1 | 0-0 | 73-21-18 | D06214J | A14 | \$D | *2 | D00881F | B10 | | | ALL | | |
| LK15 | 24 | FA | L1 | 0-0 | 28-31-11 | D06214J | A15 | \$D | *2 | D00881D | K05 | | | 050-099, 155-199, 276-299 | | |
| LK15 | 24 | FA | L1 | 0-0 | SPARE | D06214J | A15 | \$D | *2 | D00881A | REF | ** | | 150-154, 275 | | |
| LK16 | 24 | FA | L1 | 0-0 | 28-42-13 | D06214J | A16 | \$D | *2 | D00881D | K04 | | | 050-099, 155-199, 276-299 | | |
| LK16 | 24 | FA | L1 | 0-0 | SPARE | D06214J | A16 | \$D | *2 | D00881A | REF | ** | | 150-154, 275 | | |
| LK17 | 24 | FA | L1 | 0-0 | 73-21-14 | D06214J | A17 | \$D | *2 | GD00085 | S.. | 2 | | 050-099, 150-154, 275-276 | | |
| LK17 | 24 | FA | L1 | 0-0 | 73-21-14 | D06214J | A17 | \$D | *2 | GD00087 | S.. | 2 | | 155-199, 277-299 | | |
| LK18 | 24 | FA | L1 | 0-0 | 73-21-14 | D06214J | A18 | \$D | *2 | D00881D | J05 | | | ALL | | |
| LK19 | 24 | FA | L1 | 0-0 | 73-21-14 | D06214J | A19 | \$D | *2 | D00881D | J04 | | | ALL | | |
| LK20 | 24 | FA | L1 | 0-0 | 99-99-99 | D06214J | A20 | \$D | *2 | D00881A | REF | | | ALL | | |
| LM01 | 24 | FA | L2 | 0-0 | SPARE | D06214J | A01 | \$D | *2 | GD00157 | S.. | 2 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 18

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| LM02 | 24 | FA | L2 | | 0-0 | 29-32-11 | D06214J | A02 | \$D | *2 | D00883A | K04 | | | ALL |
| LM03 | 24 | FA | L2 | | 0-0 | SPARE | D06214J | A03 | \$D | *2 | D00883A | REF | ** | | 050-099, 275-299 |
| LM03 | 24 | FA | L2 | | 0-0 | SPARE | D06214J | A03 | \$D | *2 | D00883D | J02 | | | 150-199 |
| LM04 | 24 | FA | L2 | | 0-0 | SPARE | D06214J | A04 | \$D | *2 | D00883A | REF | ** | | ALL |
| LM05 | 24 | FA | L2 | | 0-0 | SPARE | D06214J | A05 | \$D | *2 | D00883B | K14 | | | 050-099, 150-199 |
| LM05 | 24 | FA | L2 | | 0-0 | 30-21-11 | D06214J | A05 | \$D | *2 | D00883E | G15 | | | 275-299 |
| LM06 | 24 | FA | L2 | | 0-0 | 28-22-21 | D06214J | A06 | \$D | *2 | D00883E | C01 | | | ALL |
| LM07 | 24 | FA | L2 | | 0-0 | SPARE | D06214J | A07 | \$D | *2 | D00883A | REF | ** | | 050-099 |
| LM07 | 24 | FA | L2 | | 0-0 | 73-33-11 | D06214J | A07 | \$D | *2 | GD00153 | A.. | 2 | | 150-154, 162-164, 275-276 |
| LM07 | 24 | FA | L2 | | 0-0 | 73-33-11 | D06214J | A07 | \$D | *2 | GDX0001 | A.. | 2 | | 155-157, 165-199, 277-299 |
| LM08 | 24 | FA | L2 | | 0-0 | 73-33-11 | D06214J | A08 | \$D | *2 | D00883D | G14 | | | ALL |
| LM09 | 24 | FA | L2 | | 0-0 | 36-22-21 | D06214J | A09 | \$D | *2 | D00883D | H15 | | | ALL |
| LM10 | 24 | FA | L2 | | 0-0 | 36-22-21 | D06214J | A10 | \$D | *2 | D00883D | H14 | | | ALL |
| LM11 | 24 | FA | L2 | | 0-0 | 79-33-11 | D06214J | A11 | \$D | *2 | D00883D | K10 | | | ALL |
| LM12 | 24 | FA | L2 | | 0-0 | 30-21-11 | D06214J | A12 | \$D | *2 | D00883E | G15 | | | 050-099, 150-199 |
| LM12 | 24 | FA | L2 | | 0-0 | SPARE | D06214J | A12 | \$D | *2 | D00883A | REF | ** | | 275-299 |
| LM13 | 24 | FA | L2 | | 0-0 | 73-33-11 | D06214J | A13 | \$D | *2 | GD00153 | A.. | 2 | | 050-099 |
| LM13 | 24 | FA | L2 | | 0-0 | SPARE | D06214J | A13 | \$D | *2 | D00883A | REF | ** | | 150-199, 275-299 |
| LM14 | 24 | FA | L2 | | 0-0 | 73-21-18 | D06214J | A14 | \$D | *2 | D00883F | B10 | | | ALL |
| LM15 | 24 | FA | L2 | | 0-0 | 28-31-11 | D06214J | A15 | \$D | *2 | D00883D | K05 | | | 050-099, 155-199, 276-299 |
| LM15 | 24 | FA | L2 | | 0-0 | SPARE | D06214J | A15 | \$D | *2 | D00883A | REF | ** | | 150-154, 275 |
| LM16 | 24 | FA | L2 | | 0-0 | 28-42-13 | D06214J | A16 | \$D | *2 | D00883D | K04 | | | 050-099, 155-199, 276-299 |
| LM16 | 24 | FA | L2 | | 0-0 | SPARE | D06214J | A16 | \$D | *2 | D00883A | REF | ** | | 150-154, 275 |
| LM17 | 24 | FA | L2 | | 0-0 | SPARE | D06214J | A17 | \$D | *2 | D00883A | REF | ** | | ALL |
| LM18 | 24 | FA | L2 | | 0-0 | 73-21-14 | D06214J | A18 | \$D | *2 | D00883D | J05 | | | ALL |
| LM19 | 24 | FA | L2 | | 0-0 | 73-21-14 | D06214J | A19 | \$D | *2 | D00883D | J04 | | | ALL |
| LM20 | 24 | FA | L2 | | 0-0 | 99-99-99 | D06214J | A20 | \$D | *2 | D00883A | REF | | | ALL |
| MK01 | 24 | FA | M2 | | 0-0 | SPARE | D06238J | A01 | \$D | *4 | GD00087 | S.. | 2 | | ALL |
| MK02 | 24 | FA | M2 | | 0-0 | 73-31-11 | D06238J | A02 | \$D | *4 | D00881D | J01 | | | ALL |
| MK03 | 24 | FA | M2 | | 0-0 | 73-31-11 | D06238J | A03 | \$D | *4 | D00881D | K01 | | | ALL |
| MK04 | 24 | FA | M2 | | 0-0 | 73-31-11 | D06238J | A04 | \$D | *4 | D00881D | H01 | | | ALL |
| MK05 | 24 | FA | M2 | | 0-0 | 79-32-11 | D06238J | A05 | \$D | *4 | D00881E | H11 | | | ALL |
| MK06 | 24 | FA | M2 | | 0-0 | SPARE | D06238J | A06 | \$D | *4 | D00881A | REF | ** | | ALL |
| MK07 | 24 | FA | M2 | | 0-0 | 79-32-11 | D06238J | A07 | \$D | *4 | D00881D | F15 | | | ALL |
| MK08 | 24 | FA | M2 | | 0-0 | SPARE | D06238J | A08 | \$D | *4 | D00881A | REF | ** | | ALL |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 19

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| MK09 | 24 | FA | M2 | 0-0 | SPARE | D06238J | A09 | \$D | *4 | D00881A | REF | ** | | ALL | | |
| MK10 | 24 | FA | M2 | 0-0 | 79-32-11 | D06238J | A10 | \$D | *4 | TB0237X | B015 | BJ | | ALL | | |
| MK11 | 24 | FA | M2 | 0-0 | 73-34-11 | D06238J | A11 | \$D | *4 | D00881D | G12 | | | 050-099, 150-199, 277-299 | | |
| MK11 | 24 | FA | M2 | 0-0 | 74-34-11 | D06238J | A11 | \$D | *4 | D00881D | G12 | | | 275-276 | | |
| MK12 | 24 | FA | M2 | 0-0 | 78-36-11 | D06238J | A12 | \$D | *4 | D00881B | G03 | | | ALL | | |
| MK13 | 24 | FA | M2 | 0-0 | 78-36-11 | D06238J | A13 | \$D | *4 | D00881B | F03 | | | ALL | | |
| MK14 | 24 | FA | M2 | 0-0 | SPARE | D06238J | A14 | \$D | *4 | D00881A | REF | ** | | ALL | | |
| MK15 | 24 | FA | M2 | 0-0 | SPARE | D06238J | A15 | \$D | *4 | D00881A | REF | ** | | ALL | | |
| MK16 | 24 | FA | M2 | 0-0 | 73-31-11 | D06238J | A16 | \$D | *4 | GD00083 | S.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| MK16 | 24 | FA | M2 | 0-0 | 73-31-11 | D06238J | A16 | \$D | *4 | GDX0002 | S.. | 2 | | 155-157, 165-199, 277-299 | | |
| MK17 | 24 | FA | M2 | 0-0 | SPARE | D06238J | A17 | \$D | *4 | D00881A | REF | ** | | ALL | | |
| MK18 | 24 | FA | M2 | 0-0 | SPARE | D06238J | A18 | \$D | *4 | D00881A | REF | ** | | ALL | | |
| MK19 | 24 | FA | M2 | 0-0 | SPARE | D06238J | A19 | \$D | *4 | D00881A | REF | ** | | ALL | | |
| MK20 | 24 | FA | M2 | 0-0 | 99-99-99 | D06238J | A20 | \$D | *4 | D00881A | REF | | | ALL | | |
| MM01 | 24 | FA | M1 | 0-0 | 99-99-99 | D06238J | A01 | \$D | *4 | D00883A | REF | | | ALL | | |
| MM02 | 24 | FA | M1 | 0-0 | 73-31-11 | D06238J | A02 | \$D | *4 | D00883D | J01 | | | ALL | | |
| MM03 | 24 | FA | M1 | 0-0 | 73-31-11 | D06238J | A03 | \$D | *4 | D00883D | K01 | | | ALL | | |
| MM04 | 24 | FA | M1 | 0-0 | 73-31-11 | D06238J | A04 | \$D | *4 | D00883D | H01 | | | ALL | | |
| MM05 | 24 | FA | M1 | 0-0 | 79-32-11 | D06238J | A05 | \$D | *4 | D00883E | H11 | | | ALL | | |
| MM06 | 24 | FA | M1 | 0-0 | 79-32-11 | D06238J | A06 | \$D | *4 | GD00153 | A.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| MM06 | 24 | FA | M1 | 0-0 | 79-32-11 | D06238J | A06 | \$D | *4 | GDX0001 | A.. | 2 | | 155-157, 165-199, 277-299 | | |
| MM07 | 24 | FA | M1 | 0-0 | 79-32-11 | D06238J | A07 | \$D | *4 | TB0237X | B015 | BJ | | ALL | | |
| MM08 | 24 | FA | M1 | 0-0 | SPARE | D06238J | A08 | \$D | *4 | D00883A | REF | ** | | 050-099, 275-299 | | |
| MM08 | 24 | FA | M1 | 0-0 | SPARE | D06238J | A08 | \$D | *4 | D00883D | H09 | | | 150-199 | | |
| MM09 | 24 | FA | M1 | 0-0 | SPARE | D06238J | A09 | \$D | *4 | D00883A | REF | ** | | 050-099, 275-299 | | |
| MM09 | 24 | FA | M1 | 0-0 | SPARE | D06238J | A09 | \$D | *4 | D00883D | H10 | | | 150-199 | | |
| MM10 | 24 | FA | M1 | 0-0 | 79-32-11 | D06238J | A10 | \$D | *4 | D00883D | F15 | | | ALL | | |
| MM11 | 24 | FA | M1 | 0-0 | 73-34-11 | D06238J | A11 | \$D | *4 | D00883D | G12 | | | ALL | | |
| MM12 | 24 | FA | M1 | 0-0 | 78-36-11 | D06238J | A12 | \$D | *4 | D00883B | G03 | | | ALL | | |
| MM13 | 24 | FA | M1 | 0-0 | 78-36-11 | D06238J | A13 | \$D | *4 | D00883B | F03 | | | ALL | | |
| MM14 | 24 | FA | M1 | 0-0 | SPARE | D06238J | A14 | \$D | *4 | D00883A | REF | ** | | ALL | | |
| MM15 | 24 | FA | M1 | 0-0 | SPARE | D06238J | A15 | \$D | *4 | GD00153 | A.. | 2 | | 050-099 | | |
| MM15 | 24 | FA | M1 | 0-0 | SPARE | D06238J | A15 | \$D | *4 | D00883A | REF | ** | | 150-199, 275-299 | | |
| MM16 | 24 | FA | M1 | 0-0 | SPARE | D06238J | A16 | \$D | *4 | D00883A | REF | ** | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 20

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|----------|---------|---------|-------|------|---------|--------|-------|------|--|--------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| MM17 | 24 | FA | M1 | 0-0 | SPARE | D06238J | A17 | \$D | *4 | D00883A | REF | ** | | ALL | |
| MM18 | 24 | FA | M1 | 0-0 | SPARE | D06238J | A18 | \$D | *4 | D00883A | REF | ** | | ALL | |
| MM19 | 24 | FA | M1 | 0-0 | SPARE | D06238J | A19 | \$D | *4 | D00883A | REF | ** | | ALL | |
| MM20 | 24 | FA | M1 | 0-0 | 99-99-99 | D06238J | A20 | \$D | *4 | D00883A | REF | | | ALL | |
| NK01 | 24 | FA | N1 | 0-0 | 99-99-99 | D06212J | A01 | \$D | *6 | D00881A | REF | | | ALL | |
| NK02 | 24 | FA | N1 | 0-0 | 21-25-21 | D06212J | A02 | \$D | *6 | D00881A | D06 | | | ALL | |
| NK03 | 24 | FA | N1 | 0-0 | 27-81-11 | D06212J | A03 | \$D | *6 | D00881A | K13 | | | ALL | |
| NK04 | 24 | FA | N1 | 0-0 | 21-61-11 | D06212J | A04 | \$D | *6 | D00881D | A14 | | | ALL | |
| NK05 | 24 | FA | N1 | 0-0 | 21-61-21 | D06212J | A05 | \$D | *6 | D00881F | K09 | | | ALL | |
| NK06 | 24 | FA | N1 | 0-0 | 21-61-31 | D06212J | A06 | \$D | *6 | D00881E | J10 | | | ALL | |
| NK07 | 24 | FA | N1 | 0-0 | 30-21-11 | D06212J | A07 | \$D | *6 | D00881D | J13 | | | 050-099, 150-199 | |
| NK07 | 24 | FA | N1 | 0-0 | SPARE | D06212J | A07 | \$D | *6 | D00881A | REF | ** | | 275-299 | |
| NK08 | 24 | FA | N1 | 0-0 | SPARE | D06212J | A08 | \$D | *6 | D00881A | REF | ** | | ALL | |
| NK09 | 24 | FA | N1 | 0-0 | 21-61-41 | D06212J | A09 | \$D | *6 | D00881D | B13 | | | ALL | |
| NK10 | 24 | FA | N1 | 0-0 | 29-33-11 | D06212J | A10 | \$D | *6 | D00881A | F05 | | | ALL | |
| NK11 | 24 | FA | N1 | 0-0 | 28-42-11 | D06212J | A11 | \$D | *6 | D00881F | H09 | | | ALL | |
| NK12 | 24 | FA | N1 | 0-0 | 29-31-11 | D06212J | A12 | \$D | *6 | D00881D | K14 | | | ALL | |
| NK13 | 24 | FA | N1 | 0-0 | 29-31-11 | D06212J | A13 | \$D | *6 | GD00083 | A.. | 2 | | 050-099, 150-154, 162-164, 275-276, 155-157, 165-199, 277-299 | |
| NK13 | 24 | FA | N1 | 0-0 | 29-31-11 | D06212J | A13 | \$D | *6 | GDX0002 | A.. | 2 | | | |
| NK14 | 24 | FA | N1 | 0-0 | 27-23-11 | D06212J | A14 | \$D | *6 | D00881D | K08 | | | ALL | |
| NK15 | 24 | FA | N1 | 0-0 | 29-11-12 | D06212J | A15 | \$D | *6 | D00881D | E14 | | | ALL | |
| NK16 | 24 | FA | N1 | 0-0 | 29-11-12 | D06212J | A16 | \$D | *6 | D00881A | K02 | | | ALL | |
| NK17 | 24 | FA | N1 | 0-0 | SPARE | D06212J | A17 | \$D | *6 | D00881A | REF | ** | | ALL | |
| NK18 | 24 | FA | N1 | 0-0 | SPARE | D06212J | A18 | \$D | *6 | D00881A | REF | ** | | ALL | |
| NK19 | 24 | FA | N1 | 0-0 | 79-35-11 | D06212J | A19 | \$D | *6 | D00881D | K03 | | | ALL | |
| NK20 | 24 | FA | N1 | 0-0 | 99-99-99 | D06212J | A20 | \$D | *6 | D00881A | REF | | | ALL | |
| NL01 | 24 | FB | N3 | 0-0 | 99-99-99 | D06212J | B01 | \$D | *6 | D00881A | REF | | | ALL | |
| NL02 | 24 | FB | N3 | 0-0 | SPARE | D06212J | B02 | \$D | *6 | D00881A | REF | ** | | ALL | |
| NL03 | 24 | FB | N3 | 0-0 | SPARE | D06212J | B03 | \$D | *6 | D00881A | REF | ** | | ALL | |
| NL04 | 24 | FB | N3 | 0-0 | SPARE | D06212J | B04 | \$D | *6 | D00881A | REF | ** | | 050-099, 275-299 | |
| NL04 | 24 | FB | N3 | 0-0 | SPARE | D06212J | B04 | \$D | *6 | D00881D | E13 | | | 150-199 | |
| NL05 | 24 | FB | N3 | 0-0 | 75-23-11 | D06212J | B05 | \$D | *6 | D00881E | J03 | | | ALL | |
| NL06 | 24 | FB | N3 | 0-0 | 77-12-11 | D06212J | B06 | \$D | *6 | D00881E | A14 | | | ALL | |
| NL07 | 24 | FB | N3 | 0-0 | 77-12-11 | D06212J | B07 | \$D | *6 | D00881E | B14 | | | ALL | |
| NL08 | 24 | FB | N3 | 0-0 | SPARE | D06212J | B08 | \$D | *6 | D00881A | REF | ** | | ALL | |
| NL09 | 24 | FB | N3 | 0-0 | SPARE | D06212J | B09 | \$D | *6 | D00881A | REF | ** | | ALL | |
| NL10 | 24 | FB | N3 | 0-0 | 79-31-11 | D06212J | B10 | \$D | *6 | D00881E | G13 | | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W2000
Page 21
Jun 06/2008



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| NL11 | 24 | FB | N3 | 0-0 | SPARE | D06212J | B11 | \$D | *6 | D00881A | REF | ** | | ALL | | |
| NL12 | 24 | FB | N3 | 0-0 | SPARE | D06212J | B12 | \$D | *6 | D00881A | REF | ** | | ALL | | |
| NL13 | 24 | FB | N3 | 0-0 | 32-09-12 | D06212J | B13 | \$D | *6 | D00881B | J13 | | | ALL | | |
| NL14 | 24 | FB | N3 | 0-0 | 32-09-12 | D06212J | B14 | \$D | *6 | D00881B | H01 | | | ALL | | |
| NL15 | 24 | FB | N3 | 0-0 | 24-11-21 | D06212J | B15 | \$D | *6 | D00881E | D08 | | | ALL | | |
| NL16 | 24 | FB | N3 | 0-0 | 30-21-11 | D06212J | B16 | \$D | *6 | D00881F | G08 | | | ALL | | |
| NL17 | 24 | FB | N3 | 0-0 | SPARE | D06212J | B17 | \$D | *6 | D00881A | REF | ** | | ALL | | |
| NL18 | 24 | FB | N3 | 0-0 | 21-44-11 | D06212J | B18 | \$D | *6 | D00881D | E01 | | | ALL | | |
| NL19 | 24 | FB | N3 | 0-0 | 29-33-11 | D06212J | B19 | \$D | *6 | D00881E | C07 | | | ALL | | |
| NL20 | 24 | FB | N3 | 0-0 | 99-99-99 | D06212J | B20 | \$D | *6 | D00881A | REF | | | ALL | | |
| NM01 | 24 | FA | N2 | 0-0 | SPARE | D06212J | A01 | \$D | *6 | GD00157 | S.. | 2 | | ALL | | |
| NM02 | 24 | FA | N2 | 0-0 | 21-25-21 | D06212J | A02 | \$D | *6 | D00883A | D06 | | | ALL | | |
| NM03 | 24 | FA | N2 | 0-0 | 27-81-11 | D06212J | A03 | \$D | *6 | D00883A | K13 | | | ALL | | |
| NM04 | 24 | FA | N2 | 0-0 | 21-61-11 | D06212J | A04 | \$D | *6 | D00883D | A14 | | | ALL | | |
| NM05 | 24 | FA | N2 | 0-0 | 21-61-21 | D06212J | A05 | \$D | *6 | D00883F | K09 | | | ALL | | |
| NM06 | 24 | FA | N2 | 0-0 | 21-61-31 | D06212J | A06 | \$D | *6 | D00883E | J10 | | | ALL | | |
| NM07 | 24 | FA | N2 | 0-0 | 30-21-11 | D06212J | A07 | \$D | *6 | D00883D | J13 | | | 050-099, 150-199 | | |
| NM07 | 24 | FA | N2 | 0-0 | SPARE | D06212J | A07 | \$D | *6 | D00883A | REF | ** | | 275-299 | | |
| NM08 | 24 | FA | N2 | 0-0 | SPARE | D06212J | A08 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| NM09 | 24 | FA | N2 | 0-0 | 21-61-41 | D06212J | A09 | \$D | *6 | D00883D | B13 | | | ALL | | |
| NM10 | 24 | FA | N2 | 0-0 | 29-33-11 | D06212J | A10 | \$D | *6 | D00883A | F05 | | | ALL | | |
| NM11 | 24 | FA | N2 | 0-0 | 28-42-11 | D06212J | A11 | \$D | *6 | D00883F | H09 | | | ALL | | |
| NM12 | 24 | FA | N2 | 0-0 | 29-31-11 | D06212J | A12 | \$D | *6 | D00883D | K14 | | | ALL | | |
| NM13 | 24 | FA | N2 | 0-0 | SPARE | D06212J | A13 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| NM14 | 24 | FA | N2 | 0-0 | 27-23-11 | D06212J | A14 | \$D | *6 | D00883D | K08 | | | ALL | | |
| NM15 | 24 | FA | N2 | 0-0 | 29-11-12 | D06212J | A15 | \$D | *6 | D00883D | E14 | | | ALL | | |
| NM16 | 24 | FA | N2 | 0-0 | 29-11-12 | D06212J | A16 | \$D | *6 | D00883A | K02 | | | ALL | | |
| NM17 | 24 | FA | N2 | 0-0 | 29-32-11 | D06212J | A17 | \$D | *6 | D00883B | J04 | | | ALL | | |
| NM18 | 24 | FA | N2 | 0-0 | 29-32-11 | D06212J | A18 | \$D | *6 | D00883B | J05 | | | ALL | | |
| NM19 | 24 | FA | N2 | 0-0 | 79-35-11 | D06212J | A19 | \$D | *6 | D00883D | K03 | | | ALL | | |
| NM20 | 24 | FA | N2 | 0-0 | 99-99-99 | D06212J | A20 | \$D | *6 | D00883A | REF | | | ALL | | |
| NN01 | 24 | FB | N4 | 0-0 | 77-12-11 | D06212J | B01 | \$D | *6 | GD00157 | S.. | 2 | | 050-099, 162-199, 277-299 | | |
| NN01 | 24 | FB | N4 | 0-0 | SPARE | D06212J | B01 | \$D | *6 | GD00157 | S.. | 2 | | 150-157, 275-276 | | |
| NN02 | 24 | FB | N4 | 0-0 | SPARE | D06212J | B02 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| NN03 | 24 | FB | N4 | 0-0 | SPARE | D06212J | B03 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| NN04 | 24 | FB | N4 | 0-0 | SPARE | D06212J | B04 | \$D | *6 | D00883A | REF | ** | | 050-099, 275-299 | | |
| NN04 | 24 | FB | N4 | 0-0 | SPARE | D06212J | B04 | \$D | *6 | D00883D | E13 | | | 150-199 | | |
| NN05 | 24 | FB | N4 | 0-0 | 75-23-11 | D06212J | B05 | \$D | *6 | D00883E | J03 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 22

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| NN06 | 24 | FB | N4 | 0-0 | 77-12-11 | D06212J | B06 | \$D | *6 | D00883E | A14 | | | ALL | | |
| NN07 | 24 | FB | N4 | 0-0 | 77-12-11 | D06212J | B07 | \$D | *6 | D00883E | B14 | | | ALL | | |
| NN08 | 24 | FB | N4 | 0-0 | SPARE | D06212J | B08 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| NN09 | 24 | FB | N4 | 0-0 | SPARE | D06212J | B09 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| NN10 | 24 | FB | N4 | 0-0 | 79-31-11 | D06212J | B10 | \$D | *6 | D00883E | G13 | | | ALL | | |
| NN11 | 24 | FB | N4 | 0-0 | 79-31-11 | D06212J | B11 | \$D | *6 | GD00153 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| NN11 | 24 | FB | N4 | 0-0 | 79-31-11 | D06212J | B11 | \$D | *6 | GDX0001 | D.. | 2 | | 155-157, 165-199, 277-299 | | |
| NN12 | 24 | FB | N4 | 0-0 | 79-31-11 | D06212J | B12 | \$D | *6 | TB0237Z | 18 | BJ | | ALL | | |
| NN13 | 24 | FB | N4 | 0-0 | 32-09-12 | D06212J | B13 | \$D | *6 | D00883B | J13 | | | ALL | | |
| NN14 | 24 | FB | N4 | 0-0 | 32-09-12 | D06212J | B14 | \$D | *6 | D00883B | H01 | | | ALL | | |
| NN15 | 24 | FB | N4 | 0-0 | 24-11-21 | D06212J | B15 | \$D | *6 | D00883E | D08 | | | ALL | | |
| NN16 | 24 | FB | N4 | 0-0 | 30-21-11 | D06212J | B16 | \$D | *6 | D00883F | G08 | | | ALL | | |
| NN17 | 24 | FB | N4 | 0-0 | SPARE | D06212J | B17 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| NN18 | 24 | FB | N4 | 0-0 | 21-44-11 | D06212J | B18 | \$D | *6 | D00883D | E01 | | | ALL | | |
| NN19 | 24 | FB | N4 | 0-0 | 29-33-11 | D06212J | B19 | \$D | *6 | D00883E | C07 | | | ALL | | |
| NN20 | 24 | FB | N4 | 0-0 | 99-99-99 | D06212J | B20 | \$D | *6 | D00883A | REF | | | ALL | | |
| PK01 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A01 | \$D | *8 | GD00087 | S.. | 2 | | ALL | | |
| PK02 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A02 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK03 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A03 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK04 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A04 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK05 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A05 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK06 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A06 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK07 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A07 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK08 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A08 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK09 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A09 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK10 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A10 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK11 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A11 | \$D | * | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| PK11 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A11 | \$D | *8 | D00881A | REF | ** | | 155-199, 277-299 | | |
| PK12 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A12 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK13 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A13 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK14 | 24 | FA | P2 | 0-0 | 21-61-51 | D06236J | A14 | \$D | *8 | D00881D | B08 | | | ALL | | |
| PK15 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A15 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK16 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A16 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK17 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A17 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK18 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A18 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PK19 | 24 | FA | P2 | 0-0 | SPARE | D06236J | A19 | \$D | *8 | D00881A | REF | ** | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 23

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| PK20 | 24 | FA | P2 | 0-0 | 99-99-99 | D06236J | A20 | \$D | *8 | D00881A | REF | | | ALL | | |
| PL01 | 24 | FB | P4 | 0-0 | 99-99-99 | D06236J | B01 | \$D | *8 | GD00087 | S.. | 2 | | 050-099, 150-154, 275-276 | | |
| PL01 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B01 | \$D | *8 | GD00087 | S.. | 2 | | 155-199, 277-299 | | |
| PL02 | 24 | FB | P4 | 0-0 | 73-21-14 | D06236J | B02 | \$D | *8 | D00881E | E14 | | | ALL | | |
| PL03 | 24 | FB | P4 | 0-0 | 73-21-14 | D06236J | B03 | \$D | *8 | D00881E | E13 | | | ALL | | |
| PL04 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B04 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL05 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B05 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL06 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B06 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL07 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B07 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL08 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B08 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL09 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B09 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL10 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B10 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL11 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B11 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL12 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B12 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL13 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B13 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL14 | 24 | FB | P4 | 0-0 | 21-51-21 | D06236J | B14 | \$D | *8 | D00881D | F11 | | | ALL | | |
| PL15 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B15 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL16 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B16 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL17 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B17 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL18 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B18 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL19 | 24 | FB | P4 | 0-0 | SPARE | D06236J | B19 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| PL20 | 24 | FB | P4 | 0-0 | 99-99-99 | D06236J | B20 | \$D | *8 | D00881A | REF | | | ALL | | |
| PM01 | 24 | FA | P1 | 0-0 | 99-99-99 | D06236J | A01 | \$D | *8 | D00883A | REF | | | ALL | | |
| PM02 | 24 | FA | P1 | 0-0 | 21-52-21 | D06236J | A02 | \$D | *8 | TB0237Z | 10 | BJ | | ALL | | |
| PM03 | 24 | FA | P1 | 0-0 | 21-52-21 | D06236J | A03 | \$D | *8 | D00883E | H13 | | | ALL | | |
| PM04 | 24 | FA | P1 | 0-0 | 21-52-21 | D06236J | A04 | \$D | *8 | GD00153 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| PM04 | 24 | FA | P1 | 0-0 | 21-52-21 | D06236J | A04 | \$D | *8 | GDX0001 | D.. | 2 | | 155-157, 165-199, 277-299 | | |
| PM05 | 24 | FA | P1 | 0-0 | 21-52-21 | D06236J | A05 | \$D | *8 | TB0237Z | 18 | BJ | | ALL | | |
| PM06 | 24 | FA | P1 | 0-0 | 21-52-21 | D06236J | A06 | \$D | *8 | D00883E | J12 | | | ALL | | |
| PM07 | 24 | FA | P1 | 0-0 | 21-52-21 | D06236J | A07 | \$D | *8 | GD00153 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| PM07 | 24 | FA | P1 | 0-0 | 21-52-21 | D06236J | A07 | \$D | *8 | GDX0001 | D.. | 2 | | 155-157, 165-199, 277-299 | | |
| PM08 | 24 | FA | P1 | 0-0 | 21-52-31 | D06236J | A08 | \$D | *8 | D00883A | F06 | | | ALL | | |
| PM09 | 24 | FA | P1 | 0-0 | 21-52-31 | D06236J | A09 | \$D | *8 | D00883A | F07 | | | ALL | | |
| PM10 | 24 | FA | P1 | 0-0 | 21-52-41 | D06236J | A10 | \$D | *8 | D00883E | E02 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 24

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|---------|-------|------|---------------------------------------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | |
| PM11 | 24 | FA | P1 | 0-0 | 21-52-41 | D06236J | A11 | \$D | * | GD00153 | D.. | 2 | 050-099, 150-154, 275-276 | | |
| PM11 | 24 | FA | P1 | 0-0 | 21-52-41 | D06236J | A11 | \$D | *8 | GDX0001 | D.. | 2 | 155-157, 165-199, 277-299 | | |
| PM11 | 24 | FA | P1 | 0-0 | 21-52-41 | D06236J | A11 | \$D | *8 | GD00153 | D.. | 2 | 162-164 | | |
| PM12 | 24 | FA | P1 | 0-0 | SPARE | D06236J | A12 | \$D | *8 | D00883A | REF | ** | ALL | | |
| PM13 | 24 | FA | P1 | 0-0 | SPARE | D06236J | A13 | \$D | *8 | D00883A | REF | ** | ALL | | |
| PM14 | 24 | FA | P1 | 0-0 | 21-61-51 | D06236J | A14 | \$D | *8 | D00883D | B08 | | ALL | | |
| PM15 | 24 | FA | P1 | 0-0 | 73-21-14 | D06236J | A15 | \$D | *8 | D00883A | E08 | | ALL | | |
| PM16 | 24 | FA | P1 | 0-0 | 36-21-11 | D06236J | A16 | \$D | *8 | D00883D | H13 | | ALL | | |
| PM17 | 24 | FA | P1 | 0-0 | 36-21-11 | D06236J | A17 | \$D | *8 | GD00153 | D.. | 2 | 050-099, 150-154, 162-164, 275-276 | | |
| PM17 | 24 | FA | P1 | 0-0 | 36-21-11 | D06236J | A17 | \$D | *8 | GDX0001 | D.. | 2 | 155-157, 165-199, 277-299 | | |
| PM18 | 24 | FA | P1 | 0-0 | 21-52-31 | D06236J | A18 | \$D | *8 | D00883A | E15 | | ALL | | |
| PM19 | 24 | FA | P1 | 0-0 | 21-52-31 | D06236J | A19 | \$D | *8 | D00883A | D15 | | ALL | | |
| PM20 | 24 | FA | P1 | 0-0 | 99-99-99 | D06236J | A20 | \$D | *8 | D00883A | REF | | ALL | | |
| PN01 | 24 | FB | P3 | 0-0 | 99-99-99 | D06236J | B01 | \$D | *8 | D00883A | REF | | ALL | | |
| PN02 | 24 | FB | P3 | 0-0 | 73-21-14 | D06236J | B02 | \$D | *8 | D00883E | E14 | | ALL | | |
| PN03 | 24 | FB | P3 | 0-0 | 73-21-14 | D06236J | B03 | \$D | *8 | D00883E | E13 | | ALL | | |
| PN04 | 24 | FB | P3 | 0-0 | 73-21-14 | D06236J | B04 | \$D | *8 | GD00153 | S.. | 2 | 050-099, 150-154, 162-164, 275-276 | | |
| PN04 | 24 | FB | P3 | 0-0 | 73-21-14 | D06236J | B04 | \$D | *8 | GDX0001 | S.. | 2 | 155-157, 165-199, 277-299 | | |
| PN05 | 24 | FB | P3 | 0-0 | 21-52-31 | D06236J | B05 | \$D | *8 | D00883F | A07 | | ALL | | |
| PN06 | 24 | FB | P3 | 0-0 | 21-52-31 | D06236J | B06 | \$D | *8 | D00883F | A08 | | ALL | | |
| PN07 | 24 | FB | P3 | 0-0 | 21-52-31 | D06236J | B07 | \$D | *8 | D00883F | C01 | | ALL | | |
| PN08 | 24 | FB | P3 | 0-0 | 21-52-31 | D06236J | B08 | \$D | *8 | D00883F | D01 | | ALL | | |
| PN09 | 24 | FB | P3 | 0-0 | 21-52-31 | D06236J | B09 | \$D | *8 | D00883D | D13 | | ALL | | |
| PN10 | 24 | FB | P3 | 0-0 | 21-52-31 | D06236J | B10 | \$D | *8 | D00883D | D14 | | ALL | | |
| PN11 | 24 | FB | P3 | 0-0 | 21-52-21 | D06236J | B11 | \$D | *8 | TB0237Z | 18 | BJ | ALL | | |
| PN12 | 24 | FB | P3 | 0-0 | 21-52-21 | D06236J | B12 | \$D | *8 | D00883E | J09 | | ALL | | |
| PN13 | 24 | FB | P3 | 0-0 | 21-52-21 | D06236J | B13 | \$D | *8 | GD00151 | D.. | 2 | 050-099, 150-154, 162-164, 275-276 | | |
| PN13 | 24 | FB | P3 | 0-0 | 21-52-21 | D06236J | B13 | \$D | *8 | GDX0001 | D.. | 2 | 155-157, 165-199, 277-299 | | |
| PN14 | 24 | FB | P3 | 0-0 | 21-51-21 | D06236J | B14 | \$D | *8 | D00883D | F11 | | ALL | | |
| PN15 | 24 | FB | P3 | 0-0 | 21-52-31 | D06236J | B15 | \$D | *8 | D00883A | F14 | | ALL | | |
| PN16 | 24 | FB | P3 | 0-0 | 21-52-31 | D06236J | B16 | \$D | *8 | D00883A | E14 | | ALL | | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 25
Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| PN17 | 24 | FB | P3 | 0-0 | SPARE | D06236J | B17 | \$D | *8 | D00883A | REF | ** | | ALL | | |
| PN18 | 24 | FB | P3 | 0-0 | SPARE | D06236J | B18 | \$D | *8 | D00883A | REF | ** | | ALL | | |
| PN19 | 24 | FB | P3 | 0-0 | SPARE | D06236J | B19 | \$D | *8 | D00883A | REF | ** | | ALL | | |
| PN20 | 24 | FB | P3 | 0-0 | 99-99-99 | D06236J | B20 | \$D | *8 | D00883A | REF | | | ALL | | |
| QK01 | 24 | FA | Q1 | 0-0 | 99-99-99 | D06230J | A01 | \$D | *F | D00881A | REF | | | ALL | | |
| QK02 | 24 | FA | Q1 | 0-0 | 78-36-21 | D06230J | A02 | \$D | *F | D00881D | H07 | | | ALL | | |
| QK03 | 24 | FA | Q1 | 0-0 | 30-31-11 | D06230J | A03 | \$D | *F | D00881E | C03 | | | ALL | | |
| QK04 | 24 | FA | Q1 | 0-0 | 30-31-11 | D06230J | A04 | \$D | *F | D00881F | B08 | | | ALL | | |
| QK05 | 24 | FA | Q1 | 0-0 | 30-31-13 | D06230J | A05 | \$D | *F | D00881D | B09 | | | ALL | | |
| QK06 | 24 | FA | Q1 | 0-0 | 30-31-13 | D06230J | A06 | \$D | *F | D00881E | K08 | | | ALL | | |
| QK07 | 24 | FA | Q1 | 0-0 | 30-32-11 | D06230J | A07 | \$D | *F | D00881D | B05 | | | ALL | | |
| QK08 | 24 | FA | Q1 | 0-0 | SPARE | D06230J | A08 | \$D | *F | D00881A | REF | ** | | ALL | | |
| QK09 | 24 | FA | Q1 | 0-0 | 30-33-11 | D06230J | A09 | \$D | *F | D00881E | A04 | | | ALL | | |
| QK10 | 24 | FA | Q1 | 0-0 | SPARE | D06230J | A10 | \$D | *F | D00881A | REF | ** | | 050-099, 275-299 | | |
| QK10 | 24 | FA | Q1 | 0-0 | SPARE | D06230J | A10 | \$D | *F | D00881B | G10 | | | 150-199 | | |
| QK11 | 24 | FA | Q1 | 0-0 | 28-42-11 | D06230J | A11 | \$D | *F | D00881F | H08 | | | ALL | | |
| QK12 | 24 | FA | Q1 | 0-0 | 30-11-11 | D06230J | A12 | \$D | *F | D00881F | G07 | | | ALL | | |
| QK13 | 24 | FA | Q1 | 0-0 | 30-11-11 | D06230J | A13 | \$D | *F | D00881F | K01 | | | ALL | | |
| QK14 | 24 | FA | Q1 | 0-0 | 30-11-11 | D06230J | A14 | \$D | *F | D00881F | J02 | | | ALL | | |
| QK15 | 24 | FA | Q1 | 0-0 | 30-11-11 | D06230J | A15 | \$D | *F | D00881F | H01 | | | ALL | | |
| QK16 | 24 | FA | Q1 | 0-0 | 21-44-21 | D06230J | A16 | \$D | *F | D00881E | C09 | | | 050-099, 150-154, 275-276 | | |
| QK16 | 24 | FA | Q1 | 0-0 | 21-44-21 | D06230J | A16 | \$D | * | D00881E | C09 | | | 155-199, 277-299 | | |
| QK17 | 24 | FA | Q1 | 0-0 | 28-42-12 | D06230J | A17 | \$D | *F | D00881B | E07 | | | 050-099, 150-154, 275-276 | | |
| QK17 | 24 | FA | Q1 | 0-0 | 28-42-12 | D06230J | A17 | \$D | * | D00881B | E07 | | | 155-199, 277-299 | | |
| QK18 | 24 | FA | Q1 | 0-0 | 27-51-11 | D06230J | A18 | \$D | *F | D00881D | A08 | | | 050-099, 150-154, 275-276 | | |
| QK18 | 24 | FA | Q1 | 0-0 | 27-51-11 | D06230J | A18 | \$D | * | D00881D | A08 | | | 155-199, 277-299 | | |
| QK19 | 24 | FA | Q1 | 0-0 | SPARE | D06230J | A19 | \$D | *F | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| QK19 | 24 | FA | Q1 | 0-0 | SPARE | D06230J | A19 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| QK20 | 24 | FA | Q1 | 0-0 | 99-99-99 | D06230J | A20 | \$D | *F | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| QK20 | 24 | FA | Q1 | 0-0 | 99-99-99 | D06230J | A20 | \$D | * | D00881A | REF | | | 155-199, 277-299 | | |
| QL01 | 24 | FB | Q3 | 0-0 | 99-99-99 | D06230J | B01 | \$D | *F | D00881A | REF | | | 050-099, 150-154 | | |
| QL01 | 24 | FB | Q3 | 0-0 | 99-99-99 | D06230J | B01 | \$D | * | D00881A | REF | | | 155-199, 277-299 | | |
| QL01 | 24 | FB | Q3 | 0-0 | 99-99-99 | D06230J | B01 | \$D | *F | D00881A | REF | ** | | 275-276 | | |
| QL02 | 24 | FB | Q3 | 0-0 | 30-81-11 | D06230J | B02 | \$D | *F | D00881E | D07 | | | 050-099, 150-154 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 26

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| QL02 | 24 | FB | Q3 | 0-0 | 30-81-11 | D06230J | B02 | \$D | * | D00881E | D07 | | | 155-199 | | |
| QL02 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B02 | \$D | *F | D00881A | REF | ** | | 275-276 | | |
| QL02 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B02 | \$D | * | D00881A | REF | ** | | 277-299 | | |
| QL03 | 24 | FB | Q3 | 0-0 | 30-81-11 | D06230J | B03 | \$D | *F | D00881B | H08 | | | 050-099, 150-154 | | |
| QL03 | 24 | FB | Q3 | 0-0 | 30-81-11 | D06230J | B03 | \$D | * | D00881B | H08 | | | 155-199 | | |
| QL03 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B03 | \$D | *F | D00881A | REF | ** | | 275-276 | | |
| QL03 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B03 | \$D | * | D00881A | REF | ** | | 277-299 | | |
| QL04 | 24 | FB | Q3 | 0-0 | 28-22-31 | D06230J | B04 | \$D | *F | D00881F | D06 | | | 050-099, 150-154, 275-276 | | |
| QL04 | 24 | FB | Q3 | 0-0 | 28-22-31 | D06230J | B04 | \$D | * | D00881F | D06 | | | 155-199, 277-299 | | |
| QL05 | 24 | FB | Q3 | 0-0 | 28-22-31 | D06230J | B05 | \$D | *F | D00881D | C14 | | | 050-099, 150-154, 275-276 | | |
| QL05 | 24 | FB | Q3 | 0-0 | 28-22-31 | D06230J | B05 | \$D | * | D00881D | C14 | | | 155-199, 277-299 | | |
| QL06 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B06 | \$D | *F | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| QL06 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B06 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| QL07 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B07 | \$D | *F | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| QL07 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B07 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| QL08 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B08 | \$D | *F | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| QL08 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B08 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| QL09 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B09 | \$D | *F | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| QL09 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B09 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| QL10 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B10 | \$D | * | D00881A | REF | ** | | ALL | | |
| QL11 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B11 | \$D | * | D00881A | REF | ** | | ALL | | |
| QL12 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B12 | \$D | * | D00881A | REF | ** | | ALL | | |
| QL13 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B13 | \$D | * | D00881A | REF | ** | | ALL | | |
| QL14 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B14 | \$D | * | D00881A | REF | ** | | ALL | | |
| QL15 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B15 | \$D | * | D00881A | REF | ** | | ALL | | |
| QL16 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B16 | \$D | * | D00881A | REF | ** | | ALL | | |
| QL17 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B17 | \$D | * | D00881A | REF | ** | | ALL | | |
| QL18 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B18 | \$D | * | D00881A | REF | ** | | ALL | | |
| QL19 | 24 | FB | Q3 | 0-0 | SPARE | D06230J | B19 | \$D | * | D00881A | REF | ** | | ALL | | |
| QL20 | 24 | FB | Q3 | 0-0 | 99-99-99 | D06230J | B20 | \$D | * | D00881A | REF | | | 050-099, 150-199, 277-299 | | |
| QL20 | 24 | FB | Q3 | 0-0 | 99-99-99 | D06230J | B20 | \$D | * | GD00085 | S.. | 2 | | 275-276 | | |
| QM01 | 24 | FA | Q2 | 0-0 | SPARE | D06230J | A01 | \$D | *F | GD00157 | S.. | 2 | | ALL | | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 27
Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| QM02 | 24 | FA | Q2 | 0-0 | 78-36-21 | D06230J | A02 | \$D | *F | D00883D | H07 | | | ALL | | |
| QM03 | 24 | FA | Q2 | 0-0 | 30-31-11 | D06230J | A03 | \$D | *F | D00883E | C03 | | | ALL | | |
| QM04 | 24 | FA | Q2 | 0-0 | 30-31-11 | D06230J | A04 | \$D | *F | D00883F | B08 | | | ALL | | |
| QM05 | 24 | FA | Q2 | 0-0 | 30-31-13 | D06230J | A05 | \$D | *F | D00883D | B09 | | | ALL | | |
| QM06 | 24 | FA | Q2 | 0-0 | 30-31-13 | D06230J | A06 | \$D | *F | D00883E | K08 | | | ALL | | |
| QM07 | 24 | FA | Q2 | 0-0 | 30-32-11 | D06230J | A07 | \$D | *F | D00883D | B05 | | | ALL | | |
| QM08 | 24 | FA | Q2 | 0-0 | SPARE | D06230J | A08 | \$D | *F | D00883A | REF | ** | | ALL | | |
| QM09 | 24 | FA | Q2 | 0-0 | 30-33-11 | D06230J | A09 | \$D | *F | D00883E | A04 | | | ALL | | |
| QM10 | 24 | FA | Q2 | 0-0 | SPARE | D06230J | A10 | \$D | *F | D00883A | REF | ** | | 050-099, 275-299 | | |
| QM10 | 24 | FA | Q2 | 0-0 | SPARE | D06230J | A10 | \$D | *F | D00883B | G10 | | | 150-199 | | |
| QM11 | 24 | FA | Q2 | 0-0 | 28-42-11 | D06230J | A11 | \$D | *F | D00883F | H08 | | | ALL | | |
| QM12 | 24 | FA | Q2 | 0-0 | 30-11-11 | D06230J | A12 | \$D | *F | D00883F | G07 | | | ALL | | |
| QM13 | 24 | FA | Q2 | 0-0 | 30-11-11 | D06230J | A13 | \$D | *F | D00883F | K01 | | | ALL | | |
| QM14 | 24 | FA | Q2 | 0-0 | 30-11-11 | D06230J | A14 | \$D | *F | D00883F | J02 | | | ALL | | |
| QM15 | 24 | FA | Q2 | 0-0 | 30-11-11 | D06230J | A15 | \$D | *F | D00883F | H01 | | | ALL | | |
| QM16 | 24 | FA | Q2 | 0-0 | 21-44-21 | D06230J | A16 | \$D | *F | D00883E | C09 | | | 050-099, 150-154, 275-276 | | |
| QM16 | 24 | FA | Q2 | 0-0 | 21-44-21 | D06230J | A16 | \$D | * | D00883E | C09 | | | 155-199, 277-299 | | |
| QM17 | 24 | FA | Q2 | 0-0 | 28-42-12 | D06230J | A17 | \$D | *F | D00883B | E07 | | | 050-099, 150-154, 275-276 | | |
| QM17 | 24 | FA | Q2 | 0-0 | 28-42-12 | D06230J | A17 | \$D | * | D00883B | E07 | | | 155-199, 277-299 | | |
| QM18 | 24 | FA | Q2 | 0-0 | 27-51-11 | D06230J | A18 | \$D | *F | D00883D | A08 | | | 050-099, 150-154, 275-276 | | |
| QM18 | 24 | FA | Q2 | 0-0 | 27-51-11 | D06230J | A18 | \$D | * | D00883D | A08 | | | 155-199, 277-299 | | |
| QM19 | 24 | FA | Q2 | 0-0 | SPARE | D06230J | A19 | \$D | *F | D00883A | REF | ** | | 050-099, 150-154, 275-276 | | |
| QM19 | 24 | FA | Q2 | 0-0 | SPARE | D06230J | A19 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | | |
| QM20 | 24 | FA | Q2 | 0-0 | 99-99-99 | D06230J | A20 | \$D | *F | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| QM20 | 24 | FA | Q2 | 0-0 | 99-99-99 | D06230J | A20 | \$D | * | D00883A | REF | | | 155-199, 277-299 | | |
| QN01 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B01 | \$D | *F | GD00157 | S.. | 2 | | 050-099, 150-154, 275-276 | | |
| QN01 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B01 | \$D | * | GD00157 | S.. | 2 | | 155-199, 277-299 | | |
| QN02 | 24 | FB | Q4 | 0-0 | 30-81-11 | D06230J | B02 | \$D | *F | D00883E | D07 | | | 050-099, 150-154 | | |
| QN02 | 24 | FB | Q4 | 0-0 | 30-81-11 | D06230J | B02 | \$D | * | D00883E | D07 | | | 155-199 | | |
| QN02 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B02 | \$D | *F | D00883A | REF | ** | | 275-276 | | |
| QN02 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B02 | \$D | * | D00883A | REF | ** | | 277-299 | | |
| QN03 | 24 | FB | Q4 | 0-0 | 30-81-11 | D06230J | B03 | \$D | *F | D00883B | H08 | | | 050-099, 150-154 | | |
| QN03 | 24 | FB | Q4 | 0-0 | 30-81-11 | D06230J | B03 | \$D | * | D00883B | H08 | | | 155-199 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 28

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------------------------------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| QN03 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B03 | \$D | *F | D00883A | REF | ** | 275-276 | | | |
| QN03 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B03 | \$D | * | D00883A | REF | ** | 277-299 | | | |
| QN04 | 24 | FB | Q4 | 0-0 | 28-22-31 | D06230J | B04 | \$D | *F | D00883F | D06 | | 050-099, 150-154, 275-276 | | | |
| QN04 | 24 | FB | Q4 | 0-0 | 28-22-31 | D06230J | B04 | \$D | * | D00883F | D06 | | 155-199, 277-299 | | | |
| QN05 | 24 | FB | Q4 | 0-0 | 28-22-31 | D06230J | B05 | \$D | *F | D00883D | C14 | | 050-099, 150-154, 275-276 | | | |
| QN05 | 24 | FB | Q4 | 0-0 | 28-22-31 | D06230J | B05 | \$D | * | D00883D | C14 | | 155-199, 277-299 | | | |
| QN06 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B06 | \$D | *F | D00883A | REF | ** | 050-099, 150-154, 275-276 | | | |
| QN06 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B06 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | | |
| QN07 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B07 | \$D | *F | D00883A | REF | ** | 050-099, 150-154, 275-276 | | | |
| QN07 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B07 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | | |
| QN08 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B08 | \$D | *F | D00883A | REF | ** | 050-099, 150-154, 275-276 | | | |
| QN08 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B08 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | | |
| QN09 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B09 | \$D | *F | D00883A | REF | ** | 050-099, 150-154, 275-276 | | | |
| QN09 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B09 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | | |
| QN10 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B10 | \$D | * | D00883A | REF | ** | ALL | | | |
| QN11 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B11 | \$D | * | D00883A | REF | ** | ALL | | | |
| QN12 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B12 | \$D | * | D00883A | REF | ** | ALL | | | |
| QN13 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B13 | \$D | * | D00883A | REF | ** | ALL | | | |
| QN14 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B14 | \$D | * | D00883A | REF | ** | ALL | | | |
| QN15 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B15 | \$D | * | D00883A | REF | ** | ALL | | | |
| QN16 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B16 | \$D | * | D00883A | REF | ** | ALL | | | |
| QN17 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B17 | \$D | * | D00883A | REF | ** | ALL | | | |
| QN18 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B18 | \$D | * | D00883A | REF | ** | ALL | | | |
| QN19 | 24 | FB | Q4 | 0-0 | SPARE | D06230J | B19 | \$D | * | D00883A | REF | ** | ALL | | | |
| QN20 | 24 | FB | Q4 | 0-0 | 99-99-99 | D06230J | B20 | \$D | * | D00883A | REF | ** | ALL | | | |
| RK01 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A01 | \$D | *A | GD00087 | S.. | 2 | 050-099, 150-154, 275-276 | | | |
| RK01 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A01 | \$D | * | GD00087 | S.. | 2 | 155-199, 277-299 | | | |
| RK02 | 24 | FA | R2 | 0-0 | 24-11-21 | D06234J | A02 | \$D | *A | D00881D | A01 | | 050-099, 150-154, 275-276 | | | |
| RK02 | 24 | FA | R2 | 0-0 | 24-11-21 | D06234J | A02 | \$D | * | D00881D | A01 | | 155-199, 277-299 | | | |
| RK03 | 24 | FA | R2 | 0-0 | 24-11-21 | D06234J | A03 | \$D | *A | D00881E | E08 | | 050-099, 150-154, 275-276 | | | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 29
Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| RK03 | 24 | FA | R2 | 0-0 | 24-11-21 | D06234J | A03 | \$D | * | D00881E | E08 | | | 155-199, 277-299 | | |
| RK04 | 24 | FA | R2 | 0-0 | 24-28-11 | D06234J | A04 | \$D | *A | D00881E | G10 | | | 050-099, 150-154, 275-276 | | |
| RK04 | 24 | FA | R2 | 0-0 | 24-28-11 | D06234J | A04 | \$D | * | D00881E | G10 | | | 155-199, 277-299 | | |
| RK05 | 24 | FA | R2 | 0-0 | 24-11-21 | D06234J | A05 | \$D | *A | D00881F | G03 | | | 050-099, 150-154, 275-276 | | |
| RK05 | 24 | FA | R2 | 0-0 | 24-11-21 | D06234J | A05 | \$D | * | D00881F | G03 | | | 155-199, 277-299 | | |
| RK06 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A06 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| RK06 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A06 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| RK07 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A07 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| RK07 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A07 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| RK08 | 24 | FA | R2 | 0-0 | 24-27-21 | D06234J | A08 | \$D | *A | D00881D | A12 | | | 050-099, 150-154, 275-276 | | |
| RK08 | 24 | FA | R2 | 0-0 | 24-27-21 | D06234J | A08 | \$D | * | D00881D | A12 | | | 155-199, 277-299 | | |
| RK09 | 24 | FA | R2 | 0-0 | 24-27-21 | D06234J | A09 | \$D | *A | D00881D | B02 | | | 050-099, 150-154, 275-276 | | |
| RK09 | 24 | FA | R2 | 0-0 | 24-27-21 | D06234J | A09 | \$D | * | D00881D | B02 | | | 155-199, 277-299 | | |
| RK10 | 24 | FA | R2 | 0-0 | 24-27-21 | D06234J | A10 | \$D | *A | D00881D | C01 | | | 050-099, 150-154, 275-276 | | |
| RK10 | 24 | FA | R2 | 0-0 | 24-27-21 | D06234J | A10 | \$D | * | D00881D | C01 | | | 155-199, 277-299 | | |
| RK11 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A11 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| RK11 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A11 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| RK12 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A12 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| RK12 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A12 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| RK13 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A13 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| RK13 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A13 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| RK14 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A14 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| RK14 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A14 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| RK15 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A15 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| RK15 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A15 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| RK16 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A16 | \$D | * | D00881A | REF | ** | | ALL | | |
| RK17 | 24 | FA | R2 | 0-0 | SPARE | D06234J | A17 | \$D | * | D00881A | REF | ** | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 30

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| RK18 | 24 | FA | R2 | | 0-0 | SPARE | D06234J | A18 | \$D | * | D00881A | REF | ** | | 050-099, 275-299 |
| RK18 | 24 | FA | R2 | | 0-0 | SPARE | D06234J | A18 | \$D | * | D00881D | H09 | | | 150-199 |
| RK19 | 24 | FA | R2 | | 0-0 | SPARE | D06234J | A19 | \$D | * | D00881A | REF | ** | | 050-099, 275-299 |
| RK19 | 24 | FA | R2 | | 0-0 | SPARE | D06234J | A19 | \$D | * | D00881D | H10 | | | 150-199 |
| RK20 | 24 | FA | R2 | | 0-0 | 99-99-99 | D06234J | A20 | \$D | * | D00881A | REF | | | ALL |
| RM01 | 24 | FA | R1 | | 0-0 | 99-99-99 | D06234J | A01 | \$D | *A | D00883A | REF | | | 050-099, 150-154, 275-276 |
| RM01 | 24 | FA | R1 | | 0-0 | 99-99-99 | D06234J | A01 | \$D | * | D00883A | REF | | | 155-199, 277-299 |
| RM02 | 24 | FA | R1 | | 0-0 | 24-11-21 | D06234J | A02 | \$D | *A | D00883D | A01 | | | 050-099, 150-154, 275-276 |
| RM02 | 24 | FA | R1 | | 0-0 | 24-11-21 | D06234J | A02 | \$D | * | D00883D | A01 | | | 155-199, 277-299 |
| RM03 | 24 | FA | R1 | | 0-0 | 24-11-21 | D06234J | A03 | \$D | *A | D00883E | E08 | | | 050-099, 150-154, 275-276 |
| RM03 | 24 | FA | R1 | | 0-0 | 24-11-21 | D06234J | A03 | \$D | * | D00883E | E08 | | | 155-199, 277-299 |
| RM04 | 24 | FA | R1 | | 0-0 | 24-28-11 | D06234J | A04 | \$D | *A | D00883E | G10 | | | 050-099, 150-154, 275-276 |
| RM04 | 24 | FA | R1 | | 0-0 | 24-28-11 | D06234J | A04 | \$D | * | D00883E | G10 | | | 155-199, 277-299 |
| RM05 | 24 | FA | R1 | | 0-0 | 24-11-21 | D06234J | A05 | \$D | *A | D00883F | G03 | | | 050-099, 150-154, 275-276 |
| RM05 | 24 | FA | R1 | | 0-0 | 24-11-21 | D06234J | A05 | \$D | * | D00883F | G03 | | | 155-199, 277-299 |
| RM06 | 24 | FA | R1 | | 0-0 | SPARE | D06234J | A06 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 |
| RM06 | 24 | FA | R1 | | 0-0 | SPARE | D06234J | A06 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 |
| RM07 | 24 | FA | R1 | | 0-0 | SPARE | D06234J | A07 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 |
| RM07 | 24 | FA | R1 | | 0-0 | SPARE | D06234J | A07 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 |
| RM08 | 24 | FA | R1 | | 0-0 | 24-27-21 | D06234J | A08 | \$D | *A | D00883D | A12 | | | 050-099, 150-154, 275-276 |
| RM08 | 24 | FA | R1 | | 0-0 | 24-27-21 | D06234J | A08 | \$D | * | D00883D | A12 | | | 155-199, 277-299 |
| RM09 | 24 | FA | R1 | | 0-0 | 24-27-21 | D06234J | A09 | \$D | *A | D00883D | B02 | | | 050-099, 150-154, 275-276 |
| RM09 | 24 | FA | R1 | | 0-0 | 24-27-21 | D06234J | A09 | \$D | * | D00883D | B02 | | | 155-199, 277-299 |
| RM10 | 24 | FA | R1 | | 0-0 | 24-27-21 | D06234J | A10 | \$D | *A | D00883D | C01 | | | 050-099, 150-154, 275-276 |
| RM10 | 24 | FA | R1 | | 0-0 | 24-27-21 | D06234J | A10 | \$D | * | D00883D | C01 | | | 155-199, 277-299 |
| RM11 | 24 | FA | R1 | | 0-0 | 24-11-21 | D06234J | A11 | \$D | *A | TB0237Z | 18 | BJ | | 050-099, 150-154, 275-276 |
| RM11 | 24 | FA | R1 | | 0-0 | 24-11-21 | D06234J | A11 | \$D | * | TB0237Z | 18 | BJ | | 155-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 31
Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2000 | 286T2000 | | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | |
| RM12 | 24 | FA | R1 | 0-0 | SPARE | D06234J | A12 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| RM12 | 24 | FA | R1 | 0-0 | SPARE | D06234J | A12 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| RM13 | 24 | FA | R1 | 0-0 | SPARE | D06234J | A13 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| RM13 | 24 | FA | R1 | 0-0 | SPARE | D06234J | A13 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| RM14 | 24 | FA | R1 | 0-0 | SPARE | D06234J | A14 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| RM14 | 24 | FA | R1 | 0-0 | SPARE | D06234J | A14 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| RM15 | 24 | FA | R1 | 0-0 | SPARE | D06234J | A15 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| RM15 | 24 | FA | R1 | 0-0 | SPARE | D06234J | A15 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| RM16 | 24 | FA | R1 | 0-0 | SPARE | D06234J | A16 | \$D | * | D00883A | REF | ** | | ALL | |
| RM17 | 24 | FA | R1 | 0-0 | SPARE | D06234J | A17 | \$D | * | D00883A | REF | ** | | ALL | |
| RM18 | 24 | FA | R1 | 0-0 | SPARE | D06234J | A18 | \$D | * | D00883A | REF | ** | | ALL | |
| RM19 | 24 | FA | R1 | 0-0 | SPARE | D06234J | A19 | \$D | * | D00883A | REF | ** | | ALL | |
| RM20 | 24 | FA | R1 | 0-0 | 99-99-99 | D06234J | A20 | \$D | * | D00883A | REF | ** | | ALL | |
| SK01 | 24 | FA | S1 | 0-0 | 99-99-99 | D06228J | A01 | \$D | *1 | D00881A | REF | | | 050-099, 150-154, 275-276 | |
| SK01 | 24 | FA | S1 | 0-0 | 99-99-99 | D06228J | A01 | \$D | *D | D00881A | REF | | | 155-199, 277-299 | |
| SK02 | 24 | FA | S1 | 0-0 | 32-61-14 | D06228J | A02 | \$D | *2 | D00881F | C07 | | | 050-099, 150-154, 275-276 | |
| SK02 | 24 | FA | S1 | 0-0 | 32-61-14 | D06228J | A02 | \$D | *D | D00881F | C07 | | | 155-199, 277-299 | |
| SK03 | 24 | FA | S1 | 0-0 | SPARE | D06228J | A03 | \$D | *3 | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| SK03 | 24 | FA | S1 | 0-0 | SPARE | D06228J | A03 | \$D | *D | D00881A | REF | ** | | 155-199, 277-299 | |
| SK04 | 24 | FA | S1 | 0-0 | SPARE | D06228J | A04 | \$D | *4 | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| SK04 | 24 | FA | S1 | 0-0 | SPARE | D06228J | A04 | \$D | *D | D00881A | REF | ** | | 155-199, 277-299 | |
| SK05 | 24 | FA | S1 | 0-0 | 32-61-14 | D06228J | A05 | \$D | *5 | D00881A | D10 | | | 050-099, 150-154, 275-276 | |
| SK05 | 24 | FA | S1 | 0-0 | 32-61-14 | D06228J | A05 | \$D | *D | D00881A | D10 | | | 155-199, 277-299 | |
| SK06 | 24 | FA | S1 | 0-0 | 32-61-14 | D06228J | A06 | \$D | *6 | D00881B | G09 | | | 050-099, 150-154, 275-276 | |
| SK06 | 24 | FA | S1 | 0-0 | 32-61-14 | D06228J | A06 | \$D | *D | D00881B | G09 | | | 155-199, 277-299 | |
| SK07 | 24 | FA | S1 | 0-0 | 32-61-14 | D06228J | A07 | \$D | *7 | D00881B | G15 | | | 050-099, 150-154, 275-276 | |
| SK07 | 24 | FA | S1 | 0-0 | 32-61-14 | D06228J | A07 | \$D | *D | D00881B | G15 | | | 155-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 32

Jun 06/2008



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| SK08 | 24 | FA | S1 | | 0-0 | 32-61-14 | D06228J | A08 | \$D | *8 | D00881E | J07 | | | 050-099, 150-154, 275-276 |
| SK08 | 24 | FA | S1 | | 0-0 | 32-61-14 | D06228J | A08 | \$D | *D | D00881E | J07 | | | 155-199, 277-299 |
| SK09 | 24 | FA | S1 | | 0-0 | 32-61-14 | D06228J | A09 | \$D | *9 | D00881B | E15 | | | 050-099, 150-154, 275-276 |
| SK09 | 24 | FA | S1 | | 0-0 | 32-61-14 | D06228J | A09 | \$D | *D | D00881B | E15 | | | 155-199, 277-299 |
| SK10 | 24 | FA | S1 | | 0-0 | 32-61-14 | D06228J | A10 | \$D | *A | D00881A | G12 | | | 050-099, 150-154, 275-276 |
| SK10 | 24 | FA | S1 | | 0-0 | 32-61-14 | D06228J | A10 | \$D | *D | D00881A | G12 | | | 155-199, 277-299 |
| SK11 | 24 | FA | S1 | | 0-0 | 32-61-14 | D06228J | A11 | \$D | *B | D00881F | C02 | | | 050-099, 150-154, 275-276 |
| SK11 | 24 | FA | S1 | | 0-0 | 32-61-14 | D06228J | A11 | \$D | *D | D00881F | C02 | | | 155-199, 277-299 |
| SK12 | 24 | FA | S1 | | 0-0 | 32-61-14 | D06228J | A12 | \$D | *C | D00881E | D11 | | | 050-099, 150-154, 275-276 |
| SK12 | 24 | FA | S1 | | 0-0 | 32-61-14 | D06228J | A12 | \$D | *D | D00881E | D11 | | | 155-199, 277-299 |
| SK13 | 24 | FA | S1 | | 0-0 | SPARE | D06228J | A13 | \$D | *D | D00881A | REF | ** | | ALL |
| SK14 | 24 | FA | S1 | | 0-0 | SPARE | D06228J | A14 | \$D | *E | D00881A | REF | ** | | 050-099, 150-154, 275-276 |
| SK14 | 24 | FA | S1 | | 0-0 | SPARE | D06228J | A14 | \$D | *D | D00881A | REF | ** | | 155-199, 277-299 |
| SK15 | 24 | FA | S1 | | 0-0 | SPARE | D06228J | A15 | \$D | *F | D00881A | REF | ** | | 050-099, 150-154, 275-276 |
| SK15 | 24 | FA | S1 | | 0-0 | SPARE | D06228J | A15 | \$D | *D | D00881A | REF | ** | | 155-199, 277-299 |
| SK16 | 24 | FA | S1 | | 0-0 | SPARE | D06228J | A16 | \$D | *G | D00881A | REF | ** | | 050-099, 150-154, 275-276 |
| SK16 | 24 | FA | S1 | | 0-0 | SPARE | D06228J | A16 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 |
| SK17 | 24 | FA | S1 | | 0-0 | SPARE | D06228J | A17 | \$D | *H | D00881A | REF | ** | | 050-099, 150-154, 275-276 |
| SK17 | 24 | FA | S1 | | 0-0 | SPARE | D06228J | A17 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 |
| SK18 | 24 | FA | S1 | | 0-0 | 77-12-12 | D06228J | A18 | \$D | *I | D00881D | J09 | | | 050-099, 150-154, 275-276 |
| SK18 | 24 | FA | S1 | | 0-0 | 77-12-12 | D06228J | A18 | \$D | * | D00881D | J09 | | | 155-199, 277-299 |
| SK19 | 24 | FA | S1 | | 0-0 | 77-12-12 | D06228J | A19 | \$D | *J | D00881D | J08 | | | 050-099, 150-154, 275-276 |
| SK19 | 24 | FA | S1 | | 0-0 | 77-12-12 | D06228J | A19 | \$D | * | D00881D | J08 | | | 155-199, 277-299 |
| SK20 | 24 | FA | S1 | | 0-0 | 99-99-99 | D06228J | A20 | \$D | *K | D00881A | REF | | | 050-099, 150-154, 275-276 |
| SK20 | 24 | FA | S1 | | 0-0 | 99-99-99 | D06228J | A20 | \$D | * | D00881A | REF | | | 155-199, 277-299 |
| SM01 | 24 | FA | S2 | | 0-0 | SPARE | D06228J | A01 | \$D | *1 | GD00157 | S.. | 2 | | 050-099, 150-154, 275-276 |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 33
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|---------------------------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| SM01 | 24 | FA | S2 | 0-0 | SPARE | D06228J | A01 | \$D | *D | GD00157 | S.. | 2 | 155-199, 277-299 | | |
| SM02 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A02 | \$D | *2 | D00883F | C07 | | 050-099, 150-154, 275-276 | | |
| SM02 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A02 | \$D | *D | D00883F | C07 | | 155-199, 277-299 | | |
| SM03 | 24 | FA | S2 | 0-0 | SPARE | D06228J | A03 | \$D | *3 | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| SM03 | 24 | FA | S2 | 0-0 | SPARE | D06228J | A03 | \$D | *D | D00883A | REF | ** | 155-199, 277-299 | | |
| SM04 | 24 | FA | S2 | 0-0 | SPARE | D06228J | A04 | \$D | *4 | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| SM04 | 24 | FA | S2 | 0-0 | SPARE | D06228J | A04 | \$D | *D | D00883A | REF | ** | 155-199, 277-299 | | |
| SM05 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A05 | \$D | *5 | D00883A | D10 | | 050-099, 150-154, 275-276 | | |
| SM05 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A05 | \$D | *D | D00883A | D10 | | 155-199, 277-299 | | |
| SM06 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A06 | \$D | *6 | D00883B | G09 | | 050-099, 150-154, 275-276 | | |
| SM06 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A06 | \$D | *D | D00883B | G09 | | 155-199, 277-299 | | |
| SM07 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A07 | \$D | *7 | D00883B | G15 | | 050-099, 150-154, 275-276 | | |
| SM07 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A07 | \$D | *D | D00883B | G15 | | 155-199, 277-299 | | |
| SM08 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A08 | \$D | *8 | D00883E | J07 | | 050-099, 150-154, 275-276 | | |
| SM08 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A08 | \$D | *D | D00883E | J07 | | 155-199, 277-299 | | |
| SM09 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A09 | \$D | *9 | D00883B | E15 | | 050-099, 150-154, 275-276 | | |
| SM09 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A09 | \$D | *D | D00883B | E15 | | 155-199, 277-299 | | |
| SM10 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A10 | \$D | *A | D00883A | G12 | | 050-099, 150-154, 275-276 | | |
| SM10 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A10 | \$D | *D | D00883A | G12 | | 155-199, 277-299 | | |
| SM11 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A11 | \$D | *B | D00883F | C02 | | 050-099, 150-154, 275-276 | | |
| SM11 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A11 | \$D | *D | D00883F | C02 | | 155-199, 277-299 | | |
| SM12 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A12 | \$D | *C | D00883E | D11 | | 050-099, 150-154, 275-276 | | |
| SM12 | 24 | FA | S2 | 0-0 | 32-61-14 | D06228J | A12 | \$D | *D | D00883E | D11 | | 155-199, 277-299 | | |
| SM13 | 24 | FA | S2 | 0-0 | SPARE | D06228J | A13 | \$D | *D | D00883A | REF | ** | ALL | | |
| SM14 | 24 | FA | S2 | 0-0 | SPARE | D06228J | A14 | \$D | *E | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| SM14 | 24 | FA | S2 | 0-0 | SPARE | D06228J | A14 | \$D | *D | D00883A | REF | ** | 155-199, 277-299 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 34

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|---------------------------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| SM15 | 24 | FA | S2 | 0-0 | SPARE | D06228J | A15 | \$D | *F | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| SM15 | 24 | FA | S2 | 0-0 | SPARE | D06228J | A15 | \$D | *D | D00883A | REF | ** | 155-199, 277-299 | | |
| SM16 | 24 | FA | S2 | 0-0 | SPARE | D06228J | A16 | \$D | *G | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| SM16 | 24 | FA | S2 | 0-0 | SPARE | D06228J | A16 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| SM17 | 24 | FA | S2 | 0-0 | 77-12-12 | D06228J | A17 | \$D | *H | GD00153 | S.. | 2 | 050-099, 150-154, 275-276 | | |
| SM17 | 24 | FA | S2 | 0-0 | 77-12-12 | D06228J | A17 | \$D | * | GDX0001 | S.. | 2 | 155-157, 165-199, 277-299 | | |
| SM17 | 24 | FA | S2 | 0-0 | 77-12-12 | D06228J | A17 | \$D | * | GD00153 | S.. | 2 | 162-164 | | |
| SM18 | 24 | FA | S2 | 0-0 | 77-12-12 | D06228J | A18 | \$D | *I | D00883D | J09 | | 050-099, 150-154, 275-276 | | |
| SM18 | 24 | FA | S2 | 0-0 | 77-12-12 | D06228J | A18 | \$D | * | D00883D | J09 | | 155-199, 277-299 | | |
| SM19 | 24 | FA | S2 | 0-0 | 77-12-12 | D06228J | A19 | \$D | *J | D00883D | J08 | | 050-099, 150-154, 275-276 | | |
| SM19 | 24 | FA | S2 | 0-0 | 77-12-12 | D06228J | A19 | \$D | * | D00883D | J08 | | 155-199, 277-299 | | |
| SM20 | 24 | FA | S2 | 0-0 | 99-99-99 | D06228J | A20 | \$D | *K | D00883A | REF | | 050-099, 150-154, 275-276 | | |
| SM20 | 24 | FA | S2 | 0-0 | 99-99-99 | D06228J | A20 | \$D | * | D00883A | REF | | 155-199, 277-299 | | |
| TK01 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A01 | \$D | *1 | GD00087 | S.. | 2 | 050-099, 150-154, 275-276 | | |
| TK01 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A01 | \$D | *B | GD00087 | S.. | 2 | 155-199, 277-299 | | |
| TK02 | 24 | FA | T2 | 0-0 | 34-12-22 | D05063J | A02 | \$D | *2 | D00881B | C15 | | 050-099, 150-154, 275-276 | | |
| TK02 | 24 | FA | T2 | 0-0 | 34-12-22 | D05063J | A02 | \$D | *B | D00881B | C15 | | 155-199, 277-299 | | |
| TK03 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A03 | \$D | *3 | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TK03 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A03 | \$D | *B | D00881A | REF | ** | 155-199, 277-299 | | |
| TK04 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A04 | \$D | *4 | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TK04 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A04 | \$D | *B | D00881A | REF | ** | 155-199, 277-299 | | |
| TK05 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A05 | \$D | *5 | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TK05 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A05 | \$D | *B | D00881A | REF | ** | 155-199, 277-299 | | |
| TK06 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A06 | \$D | *6 | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TK06 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A06 | \$D | *B | D00881A | REF | ** | 155-199, 277-299 | | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 35
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------------------------------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| TK07 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A07 | \$D | *7 | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TK07 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A07 | \$D | *B | D00881A | REF | ** | 155-199, 277-299 | | |
| TK08 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A08 | \$D | *8 | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TK08 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A08 | \$D | *B | D00881A | REF | ** | 155-199, 277-299 | | |
| TK09 | 24 | FA | T2 | 0-0 | 22-21-21 | D05063J | A09 | \$D | *9 | D00881A | D07 | | 050-099, 150-154, 275-276 | | |
| TK09 | 24 | FA | T2 | 0-0 | 22-21-21 | D05063J | A09 | \$D | *B | D00881A | D07 | | 155-199, 277-299 | | |
| TK10 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A10 | \$D | *A | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TK10 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A10 | \$D | *B | D00881A | REF | ** | 155-199, 277-299 | | |
| TK11 | 24 | FA | T2 | 0-0 | 27-09-14 | D05063J | A11 | \$D | *B | TB0237X | C008 | BJ | ALL | | |
| TK12 | 24 | FA | T2 | 0-0 | 27-09-14 | D05063J | A12 | \$D | *C | TB0237X | A007 | BJ | 050-099, 150-154, 275-276 | | |
| TK12 | 24 | FA | T2 | 0-0 | 27-09-14 | D05063J | A12 | \$D | *B | TB0237X | A007 | BJ | 155-199, 277-299 | | |
| TK13 | 24 | FA | T2 | 0-0 | 27-09-14 | D05063J | A13 | \$D | *D | TB0237X | A008 | BJ | 050-099, 150-154, 275-276 | | |
| TK13 | 24 | FA | T2 | 0-0 | 27-09-14 | D05063J | A13 | \$D | *B | TB0237X | A008 | BJ | 155-199, 277-299 | | |
| TK14 | 24 | FA | T2 | 0-0 | 31-51-11 | D05063J | A14 | \$D | *E | D00881B | C08 | | 050-099, 150-154, 275-276 | | |
| TK14 | 24 | FA | T2 | 0-0 | 31-51-11 | D05063J | A14 | \$D | *B | D00881B | C08 | | 155-199, 277-299 | | |
| TK15 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A15 | \$D | *F | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TK15 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A15 | \$D | *B | D00881A | REF | ** | 155-199, 277-299 | | |
| TK16 | 24 | FA | T2 | 0-0 | 34-21-21 | D05063J | A16 | \$D | *G | D00881D | E09 | | 050-099, 150-154, 275-276 | | |
| TK16 | 24 | FA | T2 | 0-0 | 34-21-21 | D05063J | A16 | \$D | * | D00881D | E09 | | 155-199, 277-299 | | |
| TK17 | 24 | FA | T2 | 0-0 | 34-21-21 | D05063J | A17 | \$D | *H | D00881D | E02 | | 050-099, 150-154, 275-276 | | |
| TK17 | 24 | FA | T2 | 0-0 | 34-21-21 | D05063J | A17 | \$D | * | D00881D | E02 | | 155-199, 277-299 | | |
| TK18 | 24 | FA | T2 | 0-0 | 34-21-21 | D05063J | A18 | \$D | *I | D00881D | E05 | | 050-099, 150-154, 275-276 | | |
| TK18 | 24 | FA | T2 | 0-0 | 34-21-21 | D05063J | A18 | \$D | * | D00881D | E05 | | 155-199, 277-299 | | |
| TK19 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A19 | \$D | *J | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TK19 | 24 | FA | T2 | 0-0 | SPARE | D05063J | A19 | \$D | * | D00881A | REF | ** | 155-199, 277-299 | | |
| TK20 | 24 | FA | T2 | 0-0 | 99-99-99 | D05063J | A20 | \$D | *K | D00881A | REF | | 050-099, 150-154, 275-276 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 36

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | |
| TK20 | 24 | FA | T2 | 0-0 | 99-99-99 | D05063J | A20 | \$D | * | D00881A | REF | | | 155-199, 277-299 | | |
| TL01 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B01 | \$D | *1 | GD00087 | S.. | 2 | | 050-099, 150-154, 275-276 | | |
| TL01 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B01 | \$D | * | GD00087 | S.. | 2 | | 155-199, 277-299 | | |
| TL02 | 24 | FB | T4 | 0-0 | 34-61-25 | D05063J | B02 | \$D | *2 | D00881A | G13 | | | 050-099, 150-154, 275-276 | | |
| TL02 | 24 | FB | T4 | 0-0 | 34-61-25 | D05063J | B02 | \$D | * | D00881A | G13 | | | 155-199, 277-299 | | |
| TL03 | 24 | FB | T4 | 0-0 | 34-61-25 | D05063J | B03 | \$D | *3 | D00881B | K01 | | | 050-099, 150-154, 275-276 | | |
| TL03 | 24 | FB | T4 | 0-0 | 34-61-25 | D05063J | B03 | \$D | * | D00881B | K01 | | | 155-199, 277-299 | | |
| TL04 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B04 | \$D | *4 | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| TL04 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B04 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| TL05 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B05 | \$D | *5 | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| TL05 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B05 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| TL06 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B06 | \$D | *6 | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| TL06 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B06 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| TL07 | 24 | FB | T4 | 0-0 | 27-09-14 | D05063J | B07 | \$D | *7 | TB0237X | D008 | BJ | | 050-099, 150-154, 275-276 | | |
| TL07 | 24 | FB | T4 | 0-0 | 27-09-14 | D05063J | B07 | \$D | * | TB0237X | D008 | BJ | | 155-199, 277-299 | | |
| TL08 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B08 | \$D | *8 | D00881A | REF | ** | | 050-099 | | |
| TL08 | 24 | FB | T4 | 0-0 | 34-61-16 | D05063J | B08 | \$D | *8 | D00881F | REF | ** | | 150-154, 275-276 | | |
| TL08 | 24 | FB | T4 | 0-0 | 34-61-16 | D05063J | B08 | \$D | * | D00881F | REF | ** | | 155-199, 277-299 | | |
| TL09 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B09 | \$D | *9 | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| TL09 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B09 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| TL10 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B10 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| TL10 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B10 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| TL11 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B11 | \$D | *B | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| TL11 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B11 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| TL12 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B12 | \$D | *C | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |
| TL12 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B12 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | | |
| TL13 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B13 | \$D | *D | D00881A | REF | ** | | 050-099, 150-154, 275-276 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 37

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------------------------------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| TL13 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B13 | \$D | * | D00881A | REF | ** | 155-199, 277-299 | | |
| TL14 | 24 | FB | T4 | 0-0 | 31-41-16 | D05063J | B14 | \$D | *E | D00881D | K06 | | 050-099, 150-154, 275-276 | | |
| TL14 | 24 | FB | T4 | 0-0 | 31-41-16 | D05063J | B14 | \$D | * | D00881D | K06 | | 155-199, 277-299 | | |
| TL15 | 24 | FB | T4 | 0-0 | 34-45-13 | D05063J | B15 | \$D | *F | D00881F | K03 | | 050-099, 153-154 | | |
| TL15 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B15 | \$D | *F | D00881A | REF | ** | 150-152, 275-276 | | |
| TL15 | 24 | FB | T4 | 0-0 | 34-45-13 | D05063J | B15 | \$D | * | D00881F | K03 | | 155-199, 277-299 | | |
| TL16 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B16 | \$D | *G | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TL16 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B16 | \$D | * | D00881A | REF | ** | 155-199, 277-299 | | |
| TL17 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B17 | \$D | *H | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TL17 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B17 | \$D | * | D00881A | REF | ** | 155-199, 277-299 | | |
| TL18 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B18 | \$D | *I | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TL18 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B18 | \$D | * | D00881A | REF | ** | 155-199, 277-299 | | |
| TL19 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B19 | \$D | *J | D00881A | REF | ** | 050-099, 150-154, 275-276 | | |
| TL19 | 24 | FB | T4 | 0-0 | SPARE | D05063J | B19 | \$D | * | D00881A | REF | ** | 155-199, 277-299 | | |
| TL20 | 24 | FB | T4 | 0-0 | 99-99-99 | D05063J | B20 | \$D | *K | D00881A | REF | | 050-099, 150-154, 275-276 | | |
| TL20 | 24 | FB | T4 | 0-0 | 99-99-99 | D05063J | B20 | \$D | * | D00881A | REF | | 155-199, 277-299 | | |
| TM01 | 24 | FA | T1 | 0-0 | 99-99-99 | D05063J | A01 | \$D | *1 | D00883A | REF | | 050-099, 150-154, 275-276 | | |
| TM01 | 24 | FA | T1 | 0-0 | 99-99-99 | D05063J | A01 | \$D | *B | D00883A | REF | | 155-199, 277-299 | | |
| TM02 | 24 | FA | T1 | 0-0 | 34-12-22 | D05063J | A02 | \$D | *2 | D00883B | C15 | | 050-099, 150-154, 275-276 | | |
| TM02 | 24 | FA | T1 | 0-0 | 34-12-22 | D05063J | A02 | \$D | *B | D00883B | C15 | | 155-199, 277-299 | | |
| TM03 | 24 | FA | T1 | 0-0 | 31-41-33 | D05063J | A03 | \$D | *3 | D00883E | F03 | | 050-099, 150-154, 275-276 | | |
| TM03 | 24 | FA | T1 | 0-0 | 31-41-33 | D05063J | A03 | \$D | *B | D00883E | F03 | | 155-199, 277-299 | | |
| TM04 | 24 | FA | T1 | 0-0 | 31-41-33 | D05063J | A04 | \$D | *4 | D00883E | F04 | | 050-099, 150-154, 275-276 | | |
| TM04 | 24 | FA | T1 | 0-0 | 31-41-33 | D05063J | A04 | \$D | *B | D00883E | F04 | | 155-199, 277-299 | | |
| TM05 | 24 | FA | T1 | 0-0 | 31-41-33 | D05063J | A05 | \$D | *5 | GD00153 | S.. | 2 | 050-099, 150-154, 275-276 | | |
| TM05 | 24 | FA | T1 | 0-0 | 31-41-33 | D05063J | A05 | \$D | *B | GD00153 | S.. | 2 | 155-157, 165-199, 277-299 | | |
| TM05 | 24 | FA | T1 | 0-0 | 31-41-33 | D05063J | A05 | \$D | *B | GD00153 | S.. | 2 | 162-164 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 38

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number GA CO TY | | | Fam | Description FT-IN Diagram | | From Equip Term Type Splice | | | | To Equip Term Type Splice Effectivity | | | | | | | | | |
|------------------------|-------------------------|----|----|-----|---|----------|--------------------------------|-----|-----|----|--|-----|----|--|--|------------------------------|--|--|--|--|
| W2000 | 286T2000 | | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | | | | | |
| TM06 | 24 | FA | T1 | | 0-0 | 31-41-33 | D05063J | A06 | \$D | *6 | D00883E | B10 | | | | 050-099, 150-154, 275-276 | | | | |
| TM06 | 24 | FA | T1 | | 0-0 | 31-41-33 | D05063J | A06 | \$D | *B | D00883E | B10 | | | | 155-199, 277-299 | | | | |
| TM07 | 24 | FA | T1 | | 0-0 | 31-41-33 | D05063J | A07 | \$D | *7 | D00883E | B11 | | | | 050-099, 150-154, 275-276 | | | | |
| TM07 | 24 | FA | T1 | | 0-0 | 31-41-33 | D05063J | A07 | \$D | *B | D00883E | B11 | | | | 155-199, 277-299 | | | | |
| TM08 | 24 | FA | T1 | | 0-0 | 31-41-33 | D05063J | A08 | \$D | *8 | GD00153 | S.. | 2 | | | 050-099, 150-154, 275-276 | | | | |
| TM08 | 24 | FA | T1 | | 0-0 | 31-41-33 | D05063J | A08 | \$D | *B | GD00153 | S.. | 2 | | | 155-157, 165-199, 277-299 | | | | |
| TM08 | 24 | FA | T1 | | 0-0 | 31-41-33 | D05063J | A08 | \$D | *B | GD00153 | S.. | 2 | | | 162-164 | | | | |
| TM09 | 24 | FA | T1 | | 0-0 | 22-21-21 | D05063J | A09 | \$D | *9 | D00883A | D07 | | | | 050-099, 150-154, 275-276 | | | | |
| TM09 | 24 | FA | T1 | | 0-0 | 22-21-21 | D05063J | A09 | \$D | *B | D00883A | D07 | | | | 155-199, 277-299 | | | | |
| TM10 | 24 | FA | T1 | | 0-0 | SPARE | D05063J | A10 | \$D | *A | D00883A | REF | ** | | | 050-099, 150-154, 275-276 | | | | |
| TM10 | 24 | FA | T1 | | 0-0 | SPARE | D05063J | A10 | \$D | *B | D00883A | REF | ** | | | 155-199, 277-299 | | | | |
| TM11 | 24 | FA | T1 | | 0-0 | 27-09-14 | D05063J | A11 | \$D | *B | D00883A | H14 | | | | ALL | | | | |
| TM12 | 24 | FA | T1 | | 0-0 | 27-09-14 | D05063J | A12 | \$D | *C | D00883F | D03 | | | | 050-099, 150-154, 275-276 | | | | |
| TM12 | 24 | FA | T1 | | 0-0 | 27-09-14 | D05063J | A12 | \$D | *B | D00883F | D03 | | | | 155-199, 277-299 | | | | |
| TM13 | 24 | FA | T1 | | 0-0 | 27-09-14 | D05063J | A13 | \$D | *D | D00883E | A10 | | | | 050-099, 150-154, 275-276 | | | | |
| TM13 | 24 | FA | T1 | | 0-0 | 27-09-14 | D05063J | A13 | \$D | *B | D00883E | A10 | | | | 155-199, 277-299 | | | | |
| TM14 | 24 | FA | T1 | | 0-0 | 31-51-11 | D05063J | A14 | \$D | *E | D00883B | C08 | | | | 050-099, 150-154, 275-276 | | | | |
| TM14 | 24 | FA | T1 | | 0-0 | 31-51-11 | D05063J | A14 | \$D | *B | D00883B | C08 | | | | 155-199, 277-299 | | | | |
| TM15 | 24 | FA | T1 | | 0-0 | 31-51-41 | D05063J | A15 | \$D | *F | D00883A | H15 | | | | 050-099, 150-154, 275-276 | | | | |
| TM15 | 24 | FA | T1 | | 0-0 | 31-51-41 | D05063J | A15 | \$D | *B | D00883A | H15 | | | | 155-199, 277-299 | | | | |
| TM16 | 24 | FA | T1 | | 0-0 | 34-21-21 | D05063J | A16 | \$D | *G | D00883D | E09 | | | | 050-099, 150-154, 275-276 | | | | |
| TM16 | 24 | FA | T1 | | 0-0 | 34-21-21 | D05063J | A16 | \$D | * | D00883D | E09 | | | | 155-199, 277-299 | | | | |
| TM17 | 24 | FA | T1 | | 0-0 | 34-21-21 | D05063J | A17 | \$D | *H | D00883D | E02 | | | | 050-099, 150-154, 275-276 | | | | |
| TM17 | 24 | FA | T1 | | 0-0 | 34-21-21 | D05063J | A17 | \$D | * | D00883D | E02 | | | | 155-199, 277-299 | | | | |
| TM18 | 24 | FA | T1 | | 0-0 | 34-21-21 | D05063J | A18 | \$D | *I | D00883D | E05 | | | | 050-099, 150-154, 275-276 | | | | |
| TM18 | 24 | FA | T1 | | 0-0 | 34-21-21 | D05063J | A18 | \$D | * | D00883D | E05 | | | | 155-199, 277-299 | | | | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 39
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|---------|-------|------|---------------------------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2000 | 286T2000 | | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | |
| TM19 | 24 | FA | T1 | 0-0 | SPARE | D05063J | A19 | \$D | *J | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| TM19 | 24 | FA | T1 | 0-0 | SPARE | D05063J | A19 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| TM20 | 24 | FA | T1 | 0-0 | 99-99-99 | D05063J | A20 | \$D | *K | D00883A | REF | | 050-099, 150-154, 275-276 | | |
| TM20 | 24 | FA | T1 | 0-0 | 99-99-99 | D05063J | A20 | \$D | * | D00883A | REF | | 155-199, 277-299 | | |
| TN01 | 24 | FB | T3 | 0-0 | 99-99-99 | D05063J | B01 | \$D | *1 | D00883A | REF | | 050-099, 150-154, 275-276 | | |
| TN01 | 24 | FB | T3 | 0-0 | 99-99-99 | D05063J | B01 | \$D | * | D00883A | REF | | 155-199, 277-299 | | |
| TN02 | 24 | FB | T3 | 0-0 | 34-61-25 | D05063J | B02 | \$D | *2 | D00883A | G13 | | 050-099, 150-154, 275-276 | | |
| TN02 | 24 | FB | T3 | 0-0 | 34-61-25 | D05063J | B02 | \$D | * | D00883A | G13 | | 155-199, 277-299 | | |
| TN03 | 24 | FB | T3 | 0-0 | 34-61-25 | D05063J | B03 | \$D | *3 | D00883B | K01 | | 050-099, 150-154, 275-276 | | |
| TN03 | 24 | FB | T3 | 0-0 | 34-61-25 | D05063J | B03 | \$D | * | D00883B | K01 | | 155-199, 277-299 | | |
| TN04 | 24 | FB | T3 | 0-0 | 34-61-25 | D05063J | B04 | \$D | *4 | D00883E | B08 | | 050-099, 150-154, 275-276 | | |
| TN04 | 24 | FB | T3 | 0-0 | 34-61-25 | D05063J | B04 | \$D | * | D00883E | B08 | | 155-199, 277-299 | | |
| TN05 | 24 | FB | T3 | 0-0 | 34-61-25 | D05063J | B05 | \$D | *5 | D00883E | B09 | | 050-099, 150-154, 275-276 | | |
| TN05 | 24 | FB | T3 | 0-0 | 34-61-25 | D05063J | B05 | \$D | * | D00883E | B09 | | 155-199, 277-299 | | |
| TN06 | 24 | FB | T3 | 0-0 | 34-61-25 | D05063J | B06 | \$D | *6 | GD00153 | S.. | 2 | 050-099, 150-154, 275-276 | | |
| TN06 | 24 | FB | T3 | 0-0 | 34-61-25 | D05063J | B06 | \$D | * | GDX0001 | S.. | 2 | 155-157, 165-199, 277-299 | | |
| TN06 | 24 | FB | T3 | 0-0 | 34-61-25 | D05063J | B06 | \$D | * | GD00153 | S.. | 2 | 162-164 | | |
| TN07 | 24 | FB | T3 | 0-0 | 27-09-14 | D05063J | B07 | \$D | *7 | D00883E | K09 | | 050-099, 150-154, 275-276 | | |
| TN07 | 24 | FB | T3 | 0-0 | 27-09-14 | D05063J | B07 | \$D | * | D00883E | K09 | | 155-199, 277-299 | | |
| TN08 | 24 | FB | T3 | 0-0 | 34-61-16 | D05063J | B08 | \$D | *8 | D00883A | REF | ** | 050-099 | | |
| TN08 | 24 | FB | T3 | 0-0 | 34-61-16 | D05063J | B08 | \$D | *8 | D00883F | REF | ** | 150-154, 275-276 | | |
| TN08 | 24 | FB | T3 | 0-0 | 34-61-16 | D05063J | B08 | \$D | * | D00883F | REF | ** | 155-199, 277-299 | | |
| TN09 | 24 | FB | T3 | 0-0 | 34-61-24 | D05063J | B09 | \$D | *9 | GD00153 | S.. | 2 | 050-099, 150-154, 275-276 | | |
| TN09 | 24 | FB | T3 | 0-0 | 34-61-24 | D05063J | B09 | \$D | * | GDX0001 | S.. | 2 | 155-157, 165-199, 277-299 | | |
| TN09 | 24 | FB | T3 | 0-0 | 34-61-24 | D05063J | B09 | \$D | * | GD00153 | S.. | 2 | 162-164 | | |
| TN10 | 24 | FB | T3 | 0-0 | 34-61-24 | D05063J | B10 | \$D | *A | D00883B | C10 | | 050-099, 150-154, 275-276 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 40

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2000 | 286T2000 | | | E8 SHELF-FLAT CABLE ASSY 1 (continued) | | | | | | | | | | | |
| TN10 | 24 | FB | T3 | | 0-0 | 34-61-24 | D05063J | B10 | \$D | * | D00883B | C10 | | | 155-199, 277-299 |
| TN11 | 24 | FB | T3 | | 0-0 | 34-61-24 | D05063J | B11 | \$D | *B | D00883B | C11 | | | 050-099, 150-154, 275-276 |
| TN11 | 24 | FB | T3 | | 0-0 | 34-61-24 | D05063J | B11 | \$D | * | D00883B | C11 | | | 155-199, 277-299 |
| TN12 | 24 | FB | T3 | | 0-0 | 34-61-24 | D05063J | B12 | \$D | *C | GD00153 | S.. | 2 | | 050-099, 150-154, 275-276 |
| TN12 | 24 | FB | T3 | | 0-0 | 34-61-24 | D05063J | B12 | \$D | * | GDX0001 | S.. | 2 | | 155-157, 165-199, 277-299 |
| TN12 | 24 | FB | T3 | | 0-0 | 34-61-24 | D05063J | B12 | \$D | * | GD00153 | S.. | 2 | | 162-164 |
| TN13 | 24 | FB | T3 | | 0-0 | 31-41-16 | D05063J | B13 | \$D | *D | D00883A | E10 | | | 050-099, 150-154, 275-276 |
| TN13 | 24 | FB | T3 | | 0-0 | 31-41-16 | D05063J | B13 | \$D | * | D00883A | E10 | | | 155-199, 277-299 |
| TN14 | 24 | FB | T3 | | 0-0 | 31-41-16 | D05063J | B14 | \$D | *E | D00883D | K06 | | | 050-099, 150-154, 275-276 |
| TN14 | 24 | FB | T3 | | 0-0 | 31-41-16 | D05063J | B14 | \$D | * | D00883D | K06 | | | 155-199, 277-299 |
| TN15 | 24 | FB | T3 | | 0-0 | 34-45-13 | D05063J | B15 | \$D | *F | D00883F | K03 | | | 050-099, 153-154 |
| TN15 | 24 | FB | T3 | | 0-0 | 34-45-13 | D05063J | B15 | \$D | *F | D00883A | K03 | | | 150-152 |
| TN15 | 24 | FB | T3 | | 0-0 | 34-45-13 | D05063J | B15 | \$D | * | D00883F | K03 | | | 155-199, 277-299 |
| TN15 | 24 | FB | T3 | | 0-0 | SPARE | D05063J | B15 | \$D | *F | D00883A | REF | ** | | 275-276 |
| TN16 | 24 | FB | T3 | | 0-0 | SPARE | D05063J | B16 | \$D | *G | D00883A | REF | ** | | 050-099, 150-154, 275-276 |
| TN16 | 24 | FB | T3 | | 0-0 | SPARE | D05063J | B16 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 |
| TN17 | 24 | FB | T3 | | 0-0 | SPARE | D05063J | B17 | \$D | *H | D00883A | REF | ** | | 050-099, 150-154, 275-276 |
| TN17 | 24 | FB | T3 | | 0-0 | SPARE | D05063J | B17 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 |
| TN18 | 24 | FB | T3 | | 0-0 | SPARE | D05063J | B18 | \$D | *I | D00883A | REF | ** | | 050-099, 150-154, 275-276 |
| TN18 | 24 | FB | T3 | | 0-0 | SPARE | D05063J | B18 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 |
| TN19 | 24 | FB | T3 | | 0-0 | SPARE | D05063J | B19 | \$D | *J | D00883A | REF | ** | | 050-099, 150-154, 275-276 |
| TN19 | 24 | FB | T3 | | 0-0 | SPARE | D05063J | B19 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 |
| TN20 | 24 | FB | T3 | | 0-0 | 99-99-99 | D05063J | B20 | \$D | *K | D00883A | REF | | | 050-099, 150-154, 275-276 |
| TN20 | 24 | FB | T3 | | 0-0 | 99-99-99 | D05063J | B20 | \$D | * | D00883A | REF | | | 155-199, 277-299 |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 | | | | | | | | | | | |
| AK01 | 24 | FA | A1 | | 0-0 | 99-99-99 | D05011J | A01 | \$D | *A | D00881A | REF | | | 050-099, 150-154, 275-276 |
| AK01 | 24 | FA | A1 | | 0-0 | SPARE | D05011J | A01 | \$D | * | D00881A | REF | | | 155-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 41
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2002 | 286T2002 | | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | |
| AK02 | 24 | FA | A1 | 0-0 | 34-61-14 | D05011J | A02 | \$D | *A | D00881B | C10 | | | 050-099, 150-154, 275-276 | |
| AK02 | 24 | FA | A1 | 0-0 | 34-61-14 | D05011J | A02 | \$D | * | D00881B | C10 | | | 155-199, 277-299 | |
| AK03 | 24 | FA | A1 | 0-0 | 34-61-14 | D05011J | A03 | \$D | *A | D00881B | C11 | | | 050-099, 150-154, 275-276 | |
| AK03 | 24 | FA | A1 | 0-0 | 34-61-14 | D05011J | A03 | \$D | * | D00881B | C11 | | | 155-199, 277-299 | |
| AK04 | 24 | FA | A1 | 0-0 | 34-61-14 | D05011J | A04 | \$D | *A | GD00089 | S.. | 2 | | 050-099, 150-154, 275-276 | |
| AK04 | 24 | FA | A1 | 0-0 | 34-61-14 | D05011J | A04 | \$D | * | GDX0002 | S.. | 2 | | 155-157, 165-199, 277-299 | |
| AK04 | 24 | FA | A1 | 0-0 | 34-61-14 | D05011J | A04 | \$D | * | GD00089 | S.. | 2 | | 162-164 | |
| AK05 | 24 | FA | A1 | 0-0 | 34-61-15 | D05011J | A05 | \$D | *A | D00881E | B08 | | | 050-099, 150-154, 275-276 | |
| AK05 | 24 | FA | A1 | 0-0 | 34-61-15 | D05011J | A05 | \$D | * | D00881E | B08 | | | 155-199, 277-299 | |
| AK06 | 24 | FA | A1 | 0-0 | 34-61-15 | D05011J | A06 | \$D | *A | D00881E | B09 | | | 050-099, 150-154, 275-276 | |
| AK06 | 24 | FA | A1 | 0-0 | 34-61-15 | D05011J | A06 | \$D | * | D00881E | B09 | | | 155-199, 277-299 | |
| AK07 | 24 | FA | A1 | 0-0 | 34-61-15 | D05011J | A07 | \$D | *A | GD00089 | S.. | 2 | | 050-099, 150-154, 275-276 | |
| AK07 | 24 | FA | A1 | 0-0 | 34-61-15 | D05011J | A07 | \$D | * | GD00083 | S.. | 2 | | 155-157 | |
| AK07 | 24 | FA | A1 | 0-0 | 34-61-15 | D05011J | A07 | \$D | * | GDX0002 | S.. | 2 | | 162-199, 277-299 | |
| AK08 | 24 | FA | A1 | 0-0 | 34-61-15 | D05011J | A08 | \$D | *A | D00881E | K14 | | | 050-099, 150-154, 275-276 | |
| AK08 | 24 | FA | A1 | 0-0 | 34-61-15 | D05011J | A08 | \$D | * | D00881E | K14 | | | 155-199, 277-299 | |
| AK09 | 24 | FA | A1 | 0-0 | 34-53-11 | D05011J | A09 | \$D | *A | D00881E | A13 | | | 050-099, 150-154, 275-276 | |
| AK09 | 24 | FA | A1 | 0-0 | 34-53-11 | D05011J | A09 | \$D | * | D00881E | A13 | | | 155-199, 277-299 | |
| AK10 | 24 | FA | A1 | 0-0 | SPARE | D05011J | A10 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| AK10 | 24 | FA | A1 | 0-0 | SPARE | D05011J | A10 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | |
| AK11 | 24 | FA | A1 | 0-0 | SPARE | D05011J | A11 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| AK11 | 24 | FA | A1 | 0-0 | SPARE | D05011J | A11 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | |
| AK12 | 24 | FA | A1 | 0-0 | SPARE | D05011J | A12 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| AK12 | 24 | FA | A1 | 0-0 | SPARE | D05011J | A12 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | |
| AK13 | 24 | FA | A1 | 0-0 | SPARE | D05011J | A13 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| AK13 | 24 | FA | A1 | 0-0 | SPARE | D05011J | A13 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 42

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2002 | 286T2002 | | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | |
| AK14 | 24 | FA | A1 | 0-0 | 22-14-31 | D05011J | A14 | \$D | *A | D00881E | A09 | | | 050-099, 150-154, 275-276 | |
| AK14 | 24 | FA | A1 | 0-0 | 22-14-31 | D05011J | A14 | \$D | * | D00881E | A09 | | | 155-199, 277-299 | |
| AK15 | 24 | FA | A1 | 0-0 | 34-12-62 | D05011J | A15 | \$D | *A | D00881B | K05 | | | 050-099, 150-154, 275-276 | |
| AK15 | 24 | FA | A1 | 0-0 | 34-12-62 | D05011J | A15 | \$D | * | D00881B | K05 | | | 155-199, 277-299 | |
| AK16 | 24 | FA | A1 | 0-0 | 34-12-12 | D05011J | A16 | \$D | * | D00881F | E05 | | | ALL | |
| AK17 | 24 | FA | A1 | 0-0 | 31-41-16 | D05011J | A17 | \$D | * | D00881B | J11 | | | ALL | |
| AK18 | 24 | FA | A1 | 0-0 | 34-22-38 | D05011J | A18 | \$D | * | D00881F | A09 | | | ALL | |
| AK19 | 24 | FA | A1 | 0-0 | 31-51-43 | D05011J | A19 | \$D | * | D00881B | C14 | | | ALL | |
| AK20 | 24 | FA | A1 | 0-0 | 99-99-99 | D05011J | A20 | \$D | * | D00881A | REF | | | 050-099, 150-154, 275-276 | |
| AK20 | 24 | FA | A1 | 0-0 | SPARE | D05011J | A20 | \$D | * | D00881A | REF | | | 155-199, 277-299 | |
| AM01 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A01 | \$D | *A | GD00155 | S.. | 2 | | 050-099, 150-154, 275-276 | |
| AM01 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A01 | \$D | * | GD00155 | S.. | 2 | | 155-199, 277-299 | |
| AM02 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A02 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| AM02 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A02 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| AM03 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A03 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| AM03 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A03 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| AM04 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A04 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| AM04 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A04 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| AM05 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A05 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| AM05 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A05 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| AM06 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A06 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| AM06 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A06 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| AM07 | 24 | FA | A2 | 0-0 | 34-61-15 | D05011J | A07 | \$D | *A | GD00169 | S.. | 2 | | 050-099 | |
| AM07 | 24 | FA | A2 | 0-0 | 34-61-15 | D05011J | A07 | \$D | *A | GD00153 | S.. | 2 | | 150-154, 275-276 | |
| AM07 | 24 | FA | A2 | 0-0 | 34-61-15 | D05011J | A07 | \$D | * | GD00153 | S.. | 2 | | 155-164 | |
| AM07 | 24 | FA | A2 | 0-0 | 34-61-15 | D05011J | A07 | \$D | * | GDX0001 | S.. | 2 | | 165-199, 277-299 | |
| AM08 | 24 | FA | A2 | 0-0 | 34-61-15 | D05011J | A08 | \$D | *A | D00883E | K14 | | | 050-099, 150-154, 275-276 | |
| AM08 | 24 | FA | A2 | 0-0 | 34-61-15 | D05011J | A08 | \$D | * | D00883E | K14 | | | 155-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 43
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|---------|-------|------|------|---------------------------|--|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2002 | 286T2002 | | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| AM09 | 24 | FA | A2 | 0-0 | 34-53-11 | D05011J | A09 | \$D | *A | D00883E | A13 | | | 050-099, 150-154, 275-276 | | |
| AM09 | 24 | FA | A2 | 0-0 | 34-53-11 | D05011J | A09 | \$D | * | D00883E | A13 | | | 155-199, 277-299 | | |
| AM10 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A10 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | | |
| AM10 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A10 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | | |
| AM11 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A11 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | | |
| AM11 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A11 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | | |
| AM12 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A12 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | | |
| AM12 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A12 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | | |
| AM13 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A13 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | | |
| AM13 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A13 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | | |
| AM14 | 24 | FA | A2 | 0-0 | 22-14-31 | D05011J | A14 | \$D | *A | D00883E | A09 | | | 050-099, 150-154, 275-276 | | |
| AM14 | 24 | FA | A2 | 0-0 | 22-14-31 | D05011J | A14 | \$D | * | D00883E | A09 | | | 155-199, 277-299 | | |
| AM15 | 24 | FA | A2 | 0-0 | 34-12-62 | D05011J | A15 | \$D | *A | D00883B | K05 | | | 050-099, 150-154, 275-276 | | |
| AM15 | 24 | FA | A2 | 0-0 | 34-12-62 | D05011J | A15 | \$D | * | D00883B | K05 | | | 155-199, 277-299 | | |
| AM16 | 24 | FA | A2 | 0-0 | 34-12-12 | D05011J | A16 | \$D | * | D00883F | E05 | | | ALL | | |
| AM17 | 24 | FA | A2 | 0-0 | 31-41-16 | D05011J | A17 | \$D | * | D00883B | J11 | | | ALL | | |
| AM18 | 24 | FA | A2 | 0-0 | 34-22-38 | D05011J | A18 | \$D | * | D00883F | A09 | | | ALL | | |
| AM19 | 24 | FA | A2 | 0-0 | 31-51-43 | D05011J | A19 | \$D | * | D00883B | C14 | | | ALL | | |
| AM20 | 24 | FA | A2 | 0-0 | 99-99-99 | D05011J | A20 | \$D | * | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| AM20 | 24 | FA | A2 | 0-0 | SPARE | D05011J | A20 | \$D | * | D00883A | REF | | | 155-199, 277-299 | | |
| BK01 | 24 | FA | B2 | 0-0 | SPARE | D06226J | A01 | \$D | *D | GD00085 | S.. | 2 | | 050-099, 150-154, 275-276 | | |
| BK01 | 24 | FA | B2 | 0-0 | SPARE | D06226J | A01 | \$D | * | GD00085 | S.. | 2 | | 155-199, 277-299 | | |
| BK02 | 24 | FA | B2 | 0-0 | 28-41-11 | D06226J | A02 | \$D | *D | D00881E | D04 | | | 050-099, 150-154, 275-276 | | |
| BK02 | 24 | FA | B2 | 0-0 | 28-41-11 | D06226J | A02 | \$D | * | D00881E | D04 | | | 155-199, 277-299 | | |
| BK03 | 24 | FA | B2 | 0-0 | 27-51-41 | D06226J | A03 | \$D | *D | D00881D | G15 | | | 050-099, 150-154, 275-276 | | |
| BK03 | 24 | FA | B2 | 0-0 | 27-51-41 | D06226J | A03 | \$D | * | D00881D | G15 | | | 155-199, 277-299 | | |
| BK04 | 24 | FA | B2 | 0-0 | 27-51-51 | D06226J | A04 | \$D | *D | D00881D | B15 | | | 050-099, 150-154, 275-276 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 44

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2002 | 286T2002 | | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | |
| BK04 | 24 | FA | B2 | 0-0 | 27-51-51 | D06226J | A04 | \$D | * | D00881D | B15 | | | 155-199, 277-299 | |
| BK05 | 24 | FA | B2 | 0-0 | 27-58-31 | D06226J | A05 | \$D | *D | D00881E | D01 | | | 050-099, 150-154, 275-276 | |
| BK05 | 24 | FA | B2 | 0-0 | 27-58-31 | D06226J | A05 | \$D | * | D00881E | D01 | | | 155-199, 277-299 | |
| BK06 | 24 | FA | B2 | 0-0 | SPARE | D06226J | A06 | \$D | *D | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| BK06 | 24 | FA | B2 | 0-0 | SPARE | D06226J | A06 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | |
| BK07 | 24 | FA | B2 | 0-0 | 77-31-11 | D06226J | A07 | \$D | *D | D00881E | B03 | | | 050-099, 150-154, 275-276 | |
| BK07 | 24 | FA | B2 | 0-0 | 77-31-11 | D06226J | A07 | \$D | * | D00881E | B03 | | | 155-199, 277-299 | |
| BK08 | 24 | FA | B2 | 0-0 | 77-31-11 | D06226J | A08 | \$D | *D | D00881E | B02 | | | 050-099, 150-154, 275-276 | |
| BK08 | 24 | FA | B2 | 0-0 | 77-31-11 | D06226J | A08 | \$D | * | D00881E | B02 | | | 155-199, 277-299 | |
| BK09 | 24 | FA | B2 | 0-0 | SPARE | D06226J | A09 | \$D | *D | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| BK09 | 24 | FA | B2 | 0-0 | SPARE | D06226J | A09 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | |
| BK10 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A10 | \$D | *D | D00881E | J15 | | | 050-099, 150-154, 275-276 | |
| BK10 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A10 | \$D | * | D00881E | J15 | | | 155-199, 277-299 | |
| BK11 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A11 | \$D | *D | D00881A | F10 | | | 050-099, 150-154, 275-276 | |
| BK11 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A11 | \$D | * | D00881A | F10 | | | 155-199, 277-299 | |
| BK12 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A12 | \$D | *D | D00881A | E02 | | | 050-099, 150-154, 275-276 | |
| BK12 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A12 | \$D | * | D00881A | E02 | | | 155-199, 277-299 | |
| BK13 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A13 | \$D | *D | D00881B | E03 | | | 050-099, 150-154, 275-276 | |
| BK13 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A13 | \$D | * | D00881B | E03 | | | 155-199, 277-299 | |
| BK14 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A14 | \$D | *D | D00881B | E02 | | | 050-099, 150-154, 275-276 | |
| BK14 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A14 | \$D | * | D00881B | E02 | | | 155-199, 277-299 | |
| BK15 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A15 | \$D | *D | D00881D | D06 | | | 050-099, 150-154, 275-276 | |
| BK15 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A15 | \$D | * | D00881D | D06 | | | 155-199, 277-299 | |
| BK16 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A16 | \$D | * | D00881D | D07 | | | ALL | |
| BK17 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A17 | \$D | * | D00881D | D15 | | | ALL | |
| BK18 | 24 | FA | B2 | 0-0 | 32-46-11 | D06226J | A18 | \$D | * | D00881E | H01 | | | ALL | |
| BK19 | 24 | FA | B2 | 0-0 | 28-41-13 | D06226J | A19 | \$D | * | D00881E | D13 | | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 45
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| BK20 | 24 | FA | B2 | 0-0 | 99-99-99 | D06226J | A20 | \$D | * | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| BK20 | 24 | FA | B2 | 0-0 | SPARE | D06226J | A20 | \$D | * | D00881A | REF | | | 155-199, 277-299 | | |
| BM01 | 24 | FA | B1 | 0-0 | 99-99-99 | D06226J | A01 | \$D | *D | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| BM01 | 24 | FA | B1 | 0-0 | SPARE | D06226J | A01 | \$D | * | D00883A | REF | | | 155-199, 277-299 | | |
| BM02 | 24 | FA | B1 | 0-0 | 28-41-11 | D06226J | A02 | \$D | *D | D00883E | D04 | | | 050-099, 150-154, 275-276 | | |
| BM02 | 24 | FA | B1 | 0-0 | 28-41-11 | D06226J | A02 | \$D | * | D00883E | D04 | | | 155-199, 277-299 | | |
| BM03 | 24 | FA | B1 | 0-0 | 27-51-41 | D06226J | A03 | \$D | *D | D00883D | G15 | | | 050-099, 150-154, 275-276 | | |
| BM03 | 24 | FA | B1 | 0-0 | 27-51-41 | D06226J | A03 | \$D | * | D00883D | G15 | | | 155-199, 277-299 | | |
| BM04 | 24 | FA | B1 | 0-0 | 27-51-51 | D06226J | A04 | \$D | *D | D00883D | B15 | | | 050-099, 150-154, 275-276 | | |
| BM04 | 24 | FA | B1 | 0-0 | 27-51-51 | D06226J | A04 | \$D | * | D00883D | B15 | | | 155-199, 277-299 | | |
| BM05 | 24 | FA | B1 | 0-0 | 27-58-31 | D06226J | A05 | \$D | *D | D00883E | D01 | | | 050-099, 150-154, 275-276 | | |
| BM05 | 24 | FA | B1 | 0-0 | 27-58-31 | D06226J | A05 | \$D | * | D00883E | D01 | | | 155-199, 277-299 | | |
| BM06 | 24 | FA | B1 | 0-0 | 77-31-11 | D06226J | A06 | \$D | *D | GD00169 | S.. | 2 | | 050-099, 150-154, 275-276 | | |
| BM06 | 24 | FA | B1 | 0-0 | 77-31-11 | D06226J | A06 | \$D | * | GDX0001 | S.. | 2 | | 155-157, 165-199, 277-299 | | |
| BM06 | 24 | FA | B1 | 0-0 | 77-31-11 | D06226J | A06 | \$D | * | GD00169 | S.. | 2 | | 162-164 | | |
| BM07 | 24 | FA | B1 | 0-0 | 77-31-11 | D06226J | A07 | \$D | *D | D00883E | B03 | | | 050-099, 150-154, 275-276 | | |
| BM07 | 24 | FA | B1 | 0-0 | 77-31-11 | D06226J | A07 | \$D | * | D00883E | B03 | | | 155-199, 277-299 | | |
| BM08 | 24 | FA | B1 | 0-0 | 77-31-11 | D06226J | A08 | \$D | *D | D00883E | B02 | | | 050-099, 150-154, 275-276 | | |
| BM08 | 24 | FA | B1 | 0-0 | 77-31-11 | D06226J | A08 | \$D | * | D00883E | B02 | | | 155-199, 277-299 | | |
| BM09 | 24 | FA | B1 | 0-0 | 77-31-11 | D06226J | A09 | \$D | *D | GD00169 | S.. | 2 | | 050-099, 150-154, 275-276 | | |
| BM09 | 24 | FA | B1 | 0-0 | 77-31-11 | D06226J | A09 | \$D | * | GDX0001 | S.. | 2 | | 155-157, 165-199, 277-299 | | |
| BM09 | 24 | FA | B1 | 0-0 | 77-31-11 | D06226J | A09 | \$D | * | GD00169 | S.. | 2 | | 162-164 | | |
| BM10 | 24 | FA | B1 | 0-0 | 32-46-11 | D06226J | A10 | \$D | *D | D00883E | J15 | | | 050-099, 150-154, 275-276 | | |
| BM10 | 24 | FA | B1 | 0-0 | 32-46-11 | D06226J | A10 | \$D | * | D00883E | J15 | | | 155-199, 277-299 | | |
| BM11 | 24 | FA | B1 | 0-0 | 32-46-11 | D06226J | A11 | \$D | *D | D00883A | F10 | | | 050-099, 150-154, 275-276 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 46

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| BM11 | 24 | FA | B1 | | 0-0 | 32-46-11 | D06226J | A11 | \$D | * | D00883A | F10 | | | 155-199, 277-299 |
| BM12 | 24 | FA | B1 | | 0-0 | 32-46-11 | D06226J | A12 | \$D | *D | D00883A | E02 | | | 050-099, 150-154, 275-276 |
| BM12 | 24 | FA | B1 | | 0-0 | 32-46-11 | D06226J | A12 | \$D | * | D00883A | E02 | | | 155-199, 277-299 |
| BM13 | 24 | FA | B1 | | 0-0 | 32-46-11 | D06226J | A13 | \$D | *D | D00883B | E03 | | | 050-099, 150-154, 275-276 |
| BM13 | 24 | FA | B1 | | 0-0 | 32-46-11 | D06226J | A13 | \$D | * | D00883B | E03 | | | 155-199, 277-299 |
| BM14 | 24 | FA | B1 | | 0-0 | 32-46-11 | D06226J | A14 | \$D | *D | D00883B | E02 | | | 050-099, 150-154, 275-276 |
| BM14 | 24 | FA | B1 | | 0-0 | 32-46-11 | D06226J | A14 | \$D | * | D00883B | E02 | | | 155-199, 277-299 |
| BM15 | 24 | FA | B1 | | 0-0 | 32-46-11 | D06226J | A15 | \$D | *D | D00883D | D06 | | | 050-099, 150-154, 275-276 |
| BM15 | 24 | FA | B1 | | 0-0 | 32-46-11 | D06226J | A15 | \$D | * | D00883D | D06 | | | 155-199, 277-299 |
| BM16 | 24 | FA | B1 | | 0-0 | 32-46-11 | D06226J | A16 | \$D | * | D00883D | D07 | | | ALL |
| BM17 | 24 | FA | B1 | | 0-0 | 32-46-11 | D06226J | A17 | \$D | * | D00883D | D15 | | | ALL |
| BM18 | 24 | FA | B1 | | 0-0 | 32-46-11 | D06226J | A18 | \$D | * | D00883E | H01 | | | ALL |
| BM19 | 24 | FA | B1 | | 0-0 | 28-41-13 | D06226J | A19 | \$D | * | D00883E | D13 | | | ALL |
| BM20 | 24 | FA | B1 | | 0-0 | 99-99-99 | D06226J | A20 | \$D | * | D00883A | REF | | | 050-099, 150-154, 275-276 |
| BM20 | 24 | FA | B1 | | 0-0 | SPARE | D06226J | A20 | \$D | * | D00883A | REF | | | 155-199, 277-299 |
| CK01 | 24 | FA | C1 | | 0-0 | 99-99-99 | D05009J | A01 | \$D | *6 | D00881A | REF | | | 050-099, 150-154, 275-276 |
| CK01 | 24 | FA | C1 | | 0-0 | SPARE | D05009J | A01 | \$D | *6 | D00881A | REF | | | 155-199, 277-299 |
| CK02 | 24 | FA | C1 | | 0-0 | 31-41-16 | D05009J | A02 | \$D | *6 | D00881A | E10 | | | ALL |
| CK03 | 24 | FA | C1 | | 0-0 | 31-41-31 | D05009J | A03 | \$D | *6 | D00881E | F03 | | | ALL |
| CK04 | 24 | FA | C1 | | 0-0 | 31-41-31 | D05009J | A04 | \$D | *6 | D00881E | F04 | | | ALL |
| CK05 | 24 | FA | C1 | | 0-0 | 31-41-31 | D05009J | A05 | \$D | *6 | GD00089 | S.. | 2 | | 050-099, 150-154, 162-164, 275-276 |
| CK05 | 24 | FA | C1 | | 0-0 | 31-41-31 | D05009J | A05 | \$D | *6 | GDX0002 | S.. | 2 | | 155-157, 165-199, 277-299 |
| CK06 | 24 | FA | C1 | | 0-0 | 31-41-31 | D05009J | A06 | \$D | *6 | D00881E | B10 | | | ALL |
| CK07 | 24 | FA | C1 | | 0-0 | 31-41-31 | D05009J | A07 | \$D | *6 | D00881E | B11 | | | ALL |
| CK08 | 24 | FA | C1 | | 0-0 | 31-41-31 | D05009J | A08 | \$D | *6 | GD00089 | S.. | 2 | | 050-099, 150-154, 162-164, 275-276 |
| CK08 | 24 | FA | C1 | | 0-0 | 31-41-31 | D05009J | A08 | \$D | *6 | GDX0002 | S.. | 2 | | 155-157, 165-199, 277-299 |
| CK09 | 24 | FA | C1 | | 0-0 | 22-14-31 | D05009J | A09 | \$D | *6 | D00881B | J02 | | | ALL |
| CK10 | 24 | FA | C1 | | 0-0 | 77-35-11 | D05009J | A10 | \$D | *6 | D00881D | B11 | | | ALL |
| CK11 | 24 | FA | C1 | | 0-0 | SPARE | D05009J | A11 | \$D | *6 | D00881A | REF | ** | | ALL |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 47
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| CK12 | 24 | FA | C1 | 0-0 | 22-32-12 | D05009J | A12 | \$D | *6 | D00881E | B06 | | | ALL | | |
| CK13 | 24 | FA | C1 | 0-0 | 22-32-12 | D05009J | A13 | \$D | *6 | D00881E | B07 | | | ALL | | |
| CK14 | 24 | FA | C1 | 0-0 | 22-32-12 | D05009J | A14 | \$D | *6 | GD00089 | S.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| CK14 | 24 | FA | C1 | 0-0 | 22-32-12 | D05009J | A14 | \$D | *6 | GDX0002 | S.. | 2 | | 155-157, 165-199, 277-299 | | |
| CK15 | 24 | FA | C1 | 0-0 | 22-34-11 | D05009J | A15 | \$D | *6 | D00881B | D08 | | | ALL | | |
| CK16 | 24 | FA | C1 | 0-0 | 22-41-13 | D05009J | A16 | \$D | *6 | D00881E | B04 | | | ALL | | |
| CK17 | 24 | FA | C1 | 0-0 | 22-41-13 | D05009J | A17 | \$D | *6 | D00881E | B05 | | | ALL | | |
| CK18 | 24 | FA | C1 | 0-0 | 22-41-13 | D05009J | A18 | \$D | *6 | GD00089 | S.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| CK18 | 24 | FA | C1 | 0-0 | 22-41-13 | D05009J | A18 | \$D | *6 | GDX0002 | S.. | 2 | | 155-157, 165-199, 277-299 | | |
| CK19 | 24 | FA | C1 | 0-0 | 31-31-11 | D05009J | A19 | \$D | *6 | D00881E | C10 | | | ALL | | |
| CK20 | 24 | FA | C1 | 0-0 | 99-99-99 | D05009J | A20 | \$D | *6 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| CK20 | 24 | FA | C1 | 0-0 | SPARE | D05009J | A20 | \$D | *6 | D00881A | REF | | | 155-199, 277-299 | | |
| CL01 | 24 | FB | C3 | 0-0 | 99-99-99 | D05009J | B01 | \$D | *6 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| CL01 | 24 | FB | C3 | 0-0 | SPARE | D05009J | B01 | \$D | *6 | D00881A | REF | | | 155-199, 277-299 | | |
| CL02 | 24 | FB | C3 | 0-0 | 31-31-13 | D05009J | B02 | \$D | *6 | TB0237X | B007 | BJ | | ALL | | |
| CL03 | 24 | FB | C3 | 0-0 | 31-31-13 | D05009J | B03 | \$D | *6 | TB0237X | C007 | BJ | | ALL | | |
| CL04 | 24 | FB | C3 | 0-0 | 31-31-13 | D05009J | B04 | \$D | *6 | TB0237X | D007 | BJ | | ALL | | |
| CL05 | 24 | FB | C3 | 0-0 | 31-31-13 | D05009J | B05 | \$D | *6 | TB0237X | B008 | BJ | | ALL | | |
| CL06 | 24 | FB | C3 | 0-0 | 31-51-41 | D05009J | B06 | \$D | *6 | D00881A | H15 | | | ALL | | |
| CL07 | 24 | FB | C3 | 0-0 | 31-51-41 | D05009J | B07 | \$D | *6 | D00881A | G15 | | | ALL | | |
| CL08 | 24 | FB | C3 | 0-0 | 31-51-41 | D05009J | B08 | \$D | *6 | D00881E | D02 | | | ALL | | |
| CL09 | 24 | FB | C3 | 0-0 | 31-51-41 | D05009J | B09 | \$D | *6 | D00881E | A01 | | | ALL | | |
| CL10 | 24 | FB | C3 | 0-0 | 31-51-41 | D05009J | B10 | \$D | *6 | D00881D | A15 | | | ALL | | |
| CL11 | 24 | FB | C3 | 0-0 | 31-51-42 | D05009J | B11 | \$D | *6 | D00881B | G14 | | | ALL | | |
| CL12 | 24 | FB | C3 | 0-0 | 34-16-11 | D05009J | B12 | \$D | *6 | D00881B | E14 | | | ALL | | |
| CL13 | 24 | FB | C3 | 0-0 | 34-21-11 | D05009J | B13 | \$D | *6 | D00881A | G08 | | | ALL | | |
| CL14 | 24 | FB | C3 | 0-0 | 34-21-11 | D05009J | B14 | \$D | *6 | D00881A | G05 | | | ALL | | |
| CL15 | 24 | FB | C3 | 0-0 | 34-21-11 | D05009J | B15 | \$D | *6 | D00881A | G01 | | | ALL | | |
| CL16 | 24 | FB | C3 | 0-0 | SPARE | D05009J | B16 | \$D | *6 | GD00089 | REF | # | | 050-099, 150-154, 162-164, 275-276 | | |
| CL16 | 24 | FB | C3 | 0-0 | SPARE | D05009J | B16 | \$D | *6 | GDX0002 | REF | # | | 155-157, 165-199, 277-299 | | |
| CL17 | 24 | FB | C3 | 0-0 | SPARE | D05009J | B17 | \$D | *6 | TB0237Z | CAP | Y | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 48

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| CL18 | 24 | FB | C3 | 0-0 | SPARE | D05009J | B18 | \$D | *6 | TB0237Z | CAP | Y | | ALL | | |
| CL19 | 24 | FB | C3 | 0-0 | 34-46-12 | D05009J | B19 | \$D | *6 | D00881B | J01 | | | ALL | | |
| CL20 | 24 | FB | C3 | 0-0 | 34-46-12 | D05009J | B20 | \$D | *6 | D00881A | REF | | | 050-099, 151 | | |
| CL20 | 24 | FB | C3 | 0-0 | 34-46-12 | D05009J | B20 | \$D | *6 | D00881B | G13 | | | 150, 152-199, 275-299 | | |
| CM01 | 24 | FA | C2 | 0-0 | SPARE | D05009J | A01 | \$D | *6 | GD00155 | S.. | 2 | | ALL | | |
| CM02 | 24 | FA | C2 | 0-0 | SPARE | D05009J | A02 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| CM03 | 24 | FA | C2 | 0-0 | SPARE | D05009J | A03 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| CM04 | 24 | FA | C2 | 0-0 | SPARE | D05009J | A04 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| CM05 | 24 | FA | C2 | 0-0 | SPARE | D05009J | A05 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| CM06 | 24 | FA | C2 | 0-0 | SPARE | D05009J | A06 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| CM07 | 24 | FA | C2 | 0-0 | SPARE | D05009J | A07 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| CM08 | 24 | FA | C2 | 0-0 | SPARE | D05009J | A08 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| CM09 | 24 | FA | C2 | 0-0 | 22-14-31 | D05009J | A09 | \$D | *6 | D00883B | J02 | | | ALL | | |
| CM10 | 24 | FA | C2 | 0-0 | 77-35-11 | D05009J | A10 | \$D | *6 | D00883D | B11 | | | ALL | | |
| CM11 | 24 | FA | C2 | 0-0 | SPARE | D05009J | A11 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| CM12 | 24 | FA | C2 | 0-0 | 22-32-12 | D05009J | A12 | \$D | *6 | D00883E | B06 | | | ALL | | |
| CM13 | 24 | FA | C2 | 0-0 | 22-32-12 | D05009J | A13 | \$D | *6 | D00883E | B07 | | | ALL | | |
| CM14 | 24 | FA | C2 | 0-0 | 22-32-12 | D05009J | A14 | \$D | *6 | GD00153 | S.. | 2 | | 050-099, 150-154, 275-276 | | |
| CM14 | 24 | FA | C2 | 0-0 | 22-32-12 | D05009J | A14 | \$D | *6 | GDX0001 | S.. | 2 | | 155-157, 165-199, 277-299 | | |
| CM14 | 24 | FA | C2 | 0-0 | 22-32-12 | D05009J | A14 | \$D | *6 | GD00169 | S.. | 2 | | 162-164 | | |
| CM15 | 24 | FA | C2 | 0-0 | 22-34-11 | D05009J | A15 | \$D | *6 | D00883B | D08 | | | ALL | | |
| CM16 | 24 | FA | C2 | 0-0 | 22-41-13 | D05009J | A16 | \$D | *6 | D00883E | B04 | | | ALL | | |
| CM17 | 24 | FA | C2 | 0-0 | 22-41-13 | D05009J | A17 | \$D | *6 | D00883E | B05 | | | ALL | | |
| CM18 | 24 | FA | C2 | 0-0 | 22-41-13 | D05009J | A18 | \$D | *6 | GD00169 | S.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| CM18 | 24 | FA | C2 | 0-0 | 22-41-13 | D05009J | A18 | \$D | *6 | GDX0001 | S.. | 2 | | 155-157, 165-199, 277-299 | | |
| CM19 | 24 | FA | C2 | 0-0 | 31-31-11 | D05009J | A19 | \$D | *6 | D00883E | C10 | | | ALL | | |
| CM20 | 24 | FA | C2 | 0-0 | 99-99-99 | D05009J | A20 | \$D | *6 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| CM20 | 24 | FA | C2 | 0-0 | SPARE | D05009J | A20 | \$D | *6 | D00883A | REF | | | 155-199, 277-299 | | |
| CN01 | 24 | FB | C4 | 0-0 | SPARE | D05009J | B01 | \$D | *6 | GD00155 | S.. | 2 | | ALL | | |
| CN02 | 24 | FB | C4 | 0-0 | SPARE | D05009J | B02 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| CN03 | 24 | FB | C4 | 0-0 | SPARE | D05009J | B03 | \$D | *6 | D00883A | REF | ** | | ALL | | |
| CN04 | 24 | FB | C4 | 0-0 | 31-31-13 | D05009J | B04 | \$D | *6 | GD00169 | S.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 49
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| CN04 | 24 | FB | C4 | 0-0 | 31-31-13 | D05009J | B04 | \$D | *6 | GDX0001 | S.. | 2 | | 155-157, 165-199, 277-299 | |
| CN05 | 24 | FB | C4 | 0-0 | SPARE | D05009J | B05 | \$D | *6 | D00883A | REF | ** | | ALL | |
| CN06 | 24 | FB | C4 | 0-0 | SPARE | D05009J | B06 | \$D | *6 | D00883A | REF | ** | | ALL | |
| CN07 | 24 | FB | C4 | 0-0 | 31-51-41 | D05009J | B07 | \$D | *6 | D00883A | G15 | | | ALL | |
| CN08 | 24 | FB | C4 | 0-0 | 31-51-41 | D05009J | B08 | \$D | *6 | D00883E | D02 | | | ALL | |
| CN09 | 24 | FB | C4 | 0-0 | 31-51-41 | D05009J | B09 | \$D | *6 | D00883E | A01 | | | ALL | |
| CN10 | 24 | FB | C4 | 0-0 | 31-51-41 | D05009J | B10 | \$D | *6 | D00883D | A15 | | | ALL | |
| CN11 | 24 | FB | C4 | 0-0 | 31-51-42 | D05009J | B11 | \$D | *6 | D00883B | G14 | | | ALL | |
| CN12 | 24 | FB | C4 | 0-0 | 34-16-11 | D05009J | B12 | \$D | *6 | D00883B | E14 | | | ALL | |
| CN13 | 24 | FB | C4 | 0-0 | 34-21-11 | D05009J | B13 | \$D | *6 | D00883A | G08 | | | ALL | |
| CN14 | 24 | FB | C4 | 0-0 | 34-21-11 | D05009J | B14 | \$D | *6 | D00883A | G05 | | | ALL | |
| CN15 | 24 | FB | C4 | 0-0 | 34-21-11 | D05009J | B15 | \$D | *6 | D00883A | G01 | | | ALL | |
| CN16 | 24 | FB | C4 | 0-0 | SPARE | D05009J | B16 | \$D | *6 | D00883A | REF | ** | | 050-099 | |
| CN16 | 24 | FB | C4 | 0-0 | SPARE | D05009J | B16 | \$D | *6 | GD00151 | REF | # | | 150-154, 162-164, 275-276 | |
| CN16 | 24 | FB | C4 | 0-0 | SPARE | D05009J | B16 | \$D | *6 | GDX0001 | REF | # | | 155-157, 165-199, 277-299 | |
| CN17 | 24 | FB | C4 | 0-0 | SPARE | D05009J | B17 | \$D | *6 | TB0237Z | CAP | Y | | ALL | |
| CN18 | 24 | FB | C4 | 0-0 | SPARE | D05009J | B18 | \$D | *6 | TB0237Z | CAP | Y | | ALL | |
| CN19 | 24 | FB | C4 | 0-0 | 34-46-12 | D05009J | B19 | \$D | *6 | D00883B | J01 | | | ALL | |
| CN20 | 24 | FB | C4 | 0-0 | 34-46-12 | D05009J | B20 | \$D | *6 | D00883A | REF | | | 050-099, 151 | |
| CN20 | 24 | FB | C4 | 0-0 | 34-46-12 | D05009J | B20 | \$D | *6 | D00883B | G13 | | | 150, 152-199, 275-299 | |
| DK01 | 24 | FA | D2 | 0-0 | SPARE | D06224J | A01 | \$D | *8 | GD00085 | S.. | 2 | *1 | ALL | |
| DK02 | 24 | FA | D2 | 0-0 | 32-61-14 | D06224J | A02 | \$D | *8 | D00881D | F06 | | | ALL | |
| DK03 | 24 | FA | D2 | 0-0 | SPARE | D06224J | A03 | \$D | *8 | D00881A | REF | ** | | ALL | |
| DK04 | 24 | FA | D2 | 0-0 | SPARE | D06224J | A04 | \$D | *8 | D00881A | REF | ** | | 050-099 | |
| DK04 | 24 | FA | D2 | 0-0 | 32-71-11 | D06224J | A04 | \$D | *8 | D00881F | C05 | | | 150-199, 275-299 | |
| DK05 | 24 | FA | D2 | 0-0 | 32-61-14 | D06224J | A05 | \$D | *8 | D00881D | C12 | | | ALL | |
| DK06 | 24 | FA | D2 | 0-0 | 32-61-14 | D06224J | A06 | \$D | *8 | D00881B | F09 | | | ALL | |
| DK07 | 24 | FA | D2 | 0-0 | 32-61-14 | D06224J | A07 | \$D | *8 | D00881B | F01 | | | ALL | |
| DK08 | 24 | FA | D2 | 0-0 | 32-61-14 | D06224J | A08 | \$D | *8 | D00881D | E07 | | | ALL | |
| DK09 | 24 | FA | D2 | 0-0 | 32-61-14 | D06224J | A09 | \$D | *8 | D00881D | F09 | | | ALL | |
| DK10 | 24 | FA | D2 | 0-0 | 32-61-14 | D06224J | A10 | \$D | *8 | D00881D | B07 | | | ALL | |
| DK11 | 24 | FA | D2 | 0-0 | 32-61-14 | D06224J | A11 | \$D | *8 | D00881B | F14 | | | ALL | |
| DK12 | 24 | FA | D2 | 0-0 | SPARE | D06224J | A12 | \$D | *8 | D00881A | REF | ** | | 050-099 | |
| DK12 | 24 | FA | D2 | 0-0 | 52-71-12 | D06224J | A12 | \$D | *8 | D00881A | E01 | | | 150-199, 275-299 | |
| DK13 | 24 | FA | D2 | 0-0 | SPARE | D06224J | A13 | \$D | *8 | D00881A | REF | ** | | 050-099 | |
| DK13 | 24 | FA | D2 | 0-0 | 52-71-12 | D06224J | A13 | \$D | *8 | D00881D | A09 | | | 150-199, 275-299 | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 50

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| DK14 | 24 | FA | D2 | 0-0 | 78-36-21 | D06224J | A14 | \$D | *8 | D00881D | F14 | | | ALL | | |
| DK15 | 24 | FA | D2 | 0-0 | 78-36-21 | D06224J | A15 | \$D | *8 | D00881D | F12 | | | ALL | | |
| DK16 | 24 | FA | D2 | 0-0 | 32-61-14 | D06224J | A16 | \$D | *8 | D00881A | K06 | | | ALL | | |
| DK17 | 24 | FA | D2 | 0-0 | 32-61-14 | D06224J | A17 | \$D | *8 | D00881D | G13 | | | ALL | | |
| DK18 | 24 | FA | D2 | 0-0 | 32-61-14 | D06224J | A18 | \$D | *8 | D00881D | F08 | | | ALL | | |
| DK19 | 24 | FA | D2 | 0-0 | SPARE | D06224J | A19 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| DK20 | 24 | FA | D2 | 0-0 | 99-99-99 | D06224J | A20 | \$D | *8 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| DK20 | 24 | FA | D2 | 0-0 | SPARE | D06224J | A20 | \$D | *8 | D00881A | REF | | | 155-199, 277-299 | | |
| DL01 | 24 | FB | D4 | 0-0 | SPARE | D06224J | B01 | \$D | *8 | GD00085 | S.. | 2 | *1 | ALL | | |
| DL02 | 24 | FB | D4 | 0-0 | 52-71-11 | D06224J | B02 | \$D | *8 | D00881A | D14 | | | ALL | | |
| DL03 | 24 | FB | D4 | 0-0 | 52-71-11 | D06224J | B03 | \$D | *8 | D00881A | D13 | | | ALL | | |
| DL04 | 24 | FB | D4 | 0-0 | 52-71-13 | D06224J | B04 | \$D | *8 | D00881B | C05 | | | ALL | | |
| DL05 | 24 | FB | D4 | 0-0 | 52-71-11 | D06224J | B05 | \$D | *8 | D00881B | A10 | | | ALL | | |
| DL06 | 24 | FB | D4 | 0-0 | 52-71-11 | D06224J | B06 | \$D | *8 | D00881B | E12 | | | ALL | | |
| DL07 | 24 | FB | D4 | 0-0 | 52-71-12 | D06224J | B07 | \$D | *8 | D00881B | D05 | | | 050-099 | | |
| DL07 | 24 | FB | D4 | 0-0 | 52-71-12 | D06224J | B07 | \$D | *8 | D00881A | E04 | | | 150-199, 275-299 | | |
| DL08 | 24 | FB | D4 | 0-0 | 52-71-12 | D06224J | B08 | \$D | *8 | D00881B | B10 | | | ALL | | |
| DL09 | 24 | FB | D4 | 0-0 | 52-71-12 | D06224J | B09 | \$D | *8 | D00881B | B12 | | | 050-099 | | |
| DL09 | 24 | FB | D4 | 0-0 | 52-71-12 | D06224J | B09 | \$D | *8 | D00881D | C05 | | | 150-199, 275-299 | | |
| DL10 | 24 | FB | D4 | 0-0 | 52-71-12 | D06224J | B10 | \$D | *8 | D00881B | A12 | | | ALL | | |
| DL11 | 24 | FB | D4 | 0-0 | 52-71-14 | D06224J | B11 | \$D | *8 | D00881B | B07 | | | ALL | | |
| DL12 | 24 | FB | D4 | 0-0 | 52-71-14 | D06224J | B12 | \$D | *8 | D00881B | A06 | | | ALL | | |
| DL13 | 24 | FB | D4 | 0-0 | 52-71-13 | D06224J | B13 | \$D | *8 | D00881B | A07 | | | ALL | | |
| DL14 | 24 | FB | D4 | 0-0 | 52-71-13 | D06224J | B14 | \$D | *8 | D00881F | F04 | | | ALL | | |
| DL15 | 24 | FB | D4 | 0-0 | 27-88-11 | D06224J | B15 | \$D | *8 | D00881E | B01 | | | ALL | | |
| DL16 | 24 | FB | D4 | 0-0 | 27-88-11 | D06224J | B16 | \$D | *8 | D00881D | B14 | | | ALL | | |
| DL17 | 24 | FB | D4 | 0-0 | SPARE | D06224J | B17 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| DL18 | 24 | FB | D4 | 0-0 | SPARE | D06224J | B18 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| DL19 | 24 | FB | D4 | 0-0 | SPARE | D06224J | B19 | \$D | *8 | D00881A | REF | ** | | ALL | | |
| DL20 | 24 | FB | D4 | 0-0 | 99-99-99 | D06224J | B20 | \$D | *8 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| DL20 | 24 | FB | D4 | 0-0 | SPARE | D06224J | B20 | \$D | *8 | D00881A | REF | | | 155-199, 277-299 | | |
| DM01 | 24 | FA | D1 | 0-0 | 99-99-99 | D06224J | A01 | \$D | *8 | D00883A | REF | | | ALL | | |
| DM02 | 24 | FA | D1 | 0-0 | 32-61-14 | D06224J | A02 | \$D | *8 | D00883D | F06 | | | ALL | | |
| DM03 | 24 | FA | D1 | 0-0 | SPARE | D06224J | A03 | \$D | *8 | D00883A | REF | ** | | ALL | | |
| DM04 | 24 | FA | D1 | 0-0 | SPARE | D06224J | A04 | \$D | *8 | D00883A | REF | ** | | 050-099 | | |
| DM04 | 24 | FA | D1 | 0-0 | 32-71-11 | D06224J | A04 | \$D | *8 | D00883F | C05 | | | 150-199, 275-299 | | |
| DM05 | 24 | FA | D1 | 0-0 | 32-61-14 | D06224J | A05 | \$D | *8 | D00883D | C12 | | | ALL | | |

WIRE LIST

D280T132

91-21-11
Section W2000
Page 51
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|--|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| DM06 | 24 | FA | D1 | 0-0 | 32-61-14 | D06224J | A06 | \$D | *8 | D00883B | F09 | | | ALL | | |
| DM07 | 24 | FA | D1 | 0-0 | 32-61-14 | D06224J | A07 | \$D | *8 | D00883B | F01 | | | ALL | | |
| DM08 | 24 | FA | D1 | 0-0 | 32-61-14 | D06224J | A08 | \$D | *8 | D00883D | E07 | | | ALL | | |
| DM09 | 24 | FA | D1 | 0-0 | 32-61-14 | D06224J | A09 | \$D | *8 | D00883D | F09 | | | ALL | | |
| DM10 | 24 | FA | D1 | 0-0 | 32-61-14 | D06224J | A10 | \$D | *8 | D00883D | B07 | | | ALL | | |
| DM11 | 24 | FA | D1 | 0-0 | 32-61-14 | D06224J | A11 | \$D | *8 | D00883B | F14 | | | ALL | | |
| DM12 | 24 | FA | D1 | 0-0 | SPARE | D06224J | A12 | \$D | *8 | D00883A | REF | ** | | 050-099 | | |
| DM12 | 24 | FA | D1 | 0-0 | 52-71-12 | D06224J | A12 | \$D | *8 | D00883A | E01 | | | 150-199, 275-299 | | |
| DM13 | 24 | FA | D1 | 0-0 | SPARE | D06224J | A13 | \$D | *8 | D00883A | REF | ** | | 050-099 | | |
| DM13 | 24 | FA | D1 | 0-0 | 52-71-12 | D06224J | A13 | \$D | *8 | D00883D | A09 | | | 150-199, 275-299 | | |
| DM14 | 24 | FA | D1 | 0-0 | 78-36-21 | D06224J | A14 | \$D | *8 | D00883D | F14 | | | ALL | | |
| DM15 | 24 | FA | D1 | 0-0 | 78-36-21 | D06224J | A15 | \$D | *8 | D00883D | F12 | | | ALL | | |
| DM16 | 24 | FA | D1 | 0-0 | 32-61-14 | D06224J | A16 | \$D | *8 | D00883A | K06 | | | ALL | | |
| DM17 | 24 | FA | D1 | 0-0 | 32-61-14 | D06224J | A17 | \$D | *8 | D00883D | G13 | | | ALL | | |
| DM18 | 24 | FA | D1 | 0-0 | 32-61-14 | D06224J | A18 | \$D | *8 | D00883D | F08 | | | ALL | | |
| DM19 | 24 | FA | D1 | 0-0 | SPARE | D06224J | A19 | \$D | *8 | D00883A | REF | ** | | ALL | | |
| DM20 | 24 | FA | D1 | 0-0 | 99-99-99 | D06224J | A20 | \$D | *8 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| DM20 | 24 | FA | D1 | 0-0 | SPARE | D06224J | A20 | \$D | *8 | D00883A | REF | | | 155-199, 277-299 | | |
| DN01 | 24 | FB | D3 | 0-0 | 99-99-99 | D06224J | B01 | \$D | *8 | D00883A | REF | | | ALL | | |
| DN02 | 24 | FB | D3 | 0-0 | 52-71-11 | D06224J | B02 | \$D | *8 | D00883A | D14 | | | ALL | | |
| DN03 | 24 | FB | D3 | 0-0 | 52-71-11 | D06224J | B03 | \$D | *8 | D00883A | D13 | | | ALL | | |
| DN04 | 24 | FB | D3 | 0-0 | 52-71-13 | D06224J | B04 | \$D | *8 | D00883B | C05 | | | ALL | | |
| DN05 | 24 | FB | D3 | 0-0 | 52-71-11 | D06224J | B05 | \$D | *8 | D00883B | A10 | | | ALL | | |
| DN06 | 24 | FB | D3 | 0-0 | 52-71-11 | D06224J | B06 | \$D | *8 | D00883B | E12 | | | ALL | | |
| DN07 | 24 | FB | D3 | 0-0 | 52-71-12 | D06224J | B07 | \$D | *8 | D00883B | D05 | | | 050-099 | | |
| DN07 | 24 | FB | D3 | 0-0 | 52-71-12 | D06224J | B07 | \$D | *8 | D00883A | E04 | | | 150-199, 275-299 | | |
| DN08 | 24 | FB | D3 | 0-0 | 52-71-12 | D06224J | B08 | \$D | *8 | D00883B | B10 | | | ALL | | |
| DN09 | 24 | FB | D3 | 0-0 | 52-71-12 | D06224J | B09 | \$D | *8 | D00883B | B12 | | | 050-099 | | |
| DN09 | 24 | FB | D3 | 0-0 | 52-71-12 | D06224J | B09 | \$D | *8 | D00883D | C05 | | | 150-199, 275-299 | | |
| DN10 | 24 | FB | D3 | 0-0 | 52-71-12 | D06224J | B10 | \$D | *8 | D00883B | A12 | | | ALL | | |
| DN11 | 24 | FB | D3 | 0-0 | 52-71-14 | D06224J | B11 | \$D | *8 | D00883B | B07 | | | ALL | | |
| DN12 | 24 | FB | D3 | 0-0 | 52-71-14 | D06224J | B12 | \$D | *8 | D00883B | A06 | | | ALL | | |
| DN13 | 24 | FB | D3 | 0-0 | 52-71-13 | D06224J | B13 | \$D | *8 | D00883B | A07 | | | ALL | | |
| DN14 | 24 | FB | D3 | 0-0 | 52-71-13 | D06224J | B14 | \$D | *8 | D00883F | F04 | | | ALL | | |
| DN15 | 24 | FB | D3 | 0-0 | 27-88-11 | D06224J | B15 | \$D | *8 | D00883E | B01 | | | ALL | | |
| DN16 | 24 | FB | D3 | 0-0 | 27-88-11 | D06224J | B16 | \$D | *8 | D00883D | B14 | | | ALL | | |
| DN17 | 24 | FB | D3 | 0-0 | SPARE | D06224J | B17 | \$D | *8 | D00883A | REF | ** | | ALL | | |
| DN18 | 24 | FB | D3 | 0-0 | SPARE | D06224J | B18 | \$D | *8 | D00883A | REF | ** | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 52

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| DN19 | 24 | FB | D3 | 0-0 | SPARE | D06224J | B19 | \$D | *8 | D00883A | REF | ** | | ALL | |
| DN20 | 24 | FB | D3 | 0-0 | 99-99-99 | D06224J | B20 | \$D | *8 | D00883A | REF | | | 050-099, 150-154, 275-276 | |
| DN20 | 24 | FB | D3 | 0-0 | SPARE | D06224J | B20 | \$D | *8 | D00883A | REF | | | 155-199, 277-299 | |
| EK01 | 24 | FA | E1 | 0-0 | 99-99-99 | D06200J | A01 | \$D | *1 | D00881A | REF | | | 050-099, 150-154, 275-276 | |
| EK01 | 24 | FA | E1 | 0-0 | SPARE | D06200J | A01 | \$D | *1 | D00881A | REF | | | 155-199, 277-299 | |
| EK02 | 24 | FA | E1 | 0-0 | SPARE | D06200J | A02 | \$D | *1 | D00881A | REF | ** | | ALL | |
| EK03 | 24 | FA | E1 | 0-0 | 21-31-11 | D06200J | A03 | \$D | *1 | D00881E | F14 | | | ALL | |
| EK04 | 24 | FA | E1 | 0-0 | 28-41-13 | D06200J | A04 | \$D | *1 | D00881E | D03 | | | ALL | |
| EK05 | 24 | FA | E1 | 0-0 | 80-11-11 | D06200J | A05 | \$D | *1 | D00881F | D09 | | | ALL | |
| EK06 | 24 | FA | E1 | 0-0 | 80-11-11 | D06200J | A06 | \$D | *1 | D00881B | H11 | | | ALL | |
| EK07 | 24 | FA | E1 | 0-0 | 28-42-12 | D06200J | A07 | \$D | *1 | D00881F | J09 | | | ALL | |
| EK08 | 24 | FA | E1 | 0-0 | SPARE | D06200J | A08 | \$D | *1 | D00881A | REF | ** | | ALL | |
| EK09 | 24 | FA | E1 | 0-0 | SPARE | D06200J | A09 | \$D | *1 | D00881A | REF | ** | | ALL | |
| EK10 | 24 | FA | E1 | 0-0 | SPARE | D06200J | A10 | \$D | *1 | D00881A | REF | ** | | ALL | |
| EK11 | 24 | FA | E1 | 0-0 | 36-11-11 | D06200J | A11 | \$D | *1 | D00881B | G11 | | | ALL | |
| EK12 | 24 | FA | E1 | 0-0 | 21-64-11 | D06200J | A12 | \$D | *1 | GD00089 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 | |
| EK12 | 24 | FA | E1 | 0-0 | 21-64-11 | D06200J | A12 | \$D | *1 | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 | |
| EK13 | 24 | FA | E1 | 0-0 | 21-64-11 | D06200J | A13 | \$D | *1 | D00881F | B09 | | | ALL | |
| EK14 | 24 | FA | E1 | 0-0 | 21-64-11 | D06200J | A14 | \$D | *1 | TB0237Z | 9 | BJ | | ALL | |
| EK15 | 24 | FA | E1 | 0-0 | 21-33-11 | D06200J | A15 | \$D | *1 | D00881A | F13 | | | ALL | |
| EK16 | 24 | FA | E1 | 0-0 | 74-31-11 | D06200J | A16 | \$D | *1 | D00881B | H15 | | | ALL | |
| EK17 | 24 | FA | E1 | 0-0 | 24-51-42 | D06200J | A17 | \$D | *1 | D00881B | J14 | | | ALL | |
| EK18 | 24 | FA | E1 | 0-0 | 24-11-11 | D06200J | A18 | \$D | *1 | D00881B | B05 | | | ALL | |
| EK19 | 24 | FA | E1 | 0-0 | SPARE | D06200J | A19 | \$D | *1 | D00881A | REF | ** | | 050-099, 275-299 | |
| EK19 | 24 | FA | E1 | 0-0 | SPARE | D06200J | A19 | \$D | *1 | D00881F | G02 | | | 150-199 | |
| EK20 | 24 | FA | E1 | 0-0 | 99-99-99 | D06200J | A20 | \$D | *1 | D00881A | REF | | | 050-099, 150-154, 275-276 | |
| EK20 | 24 | FA | E1 | 0-0 | SPARE | D06200J | A20 | \$D | *1 | D00881A | REF | | | 155-199, 277-299 | |
| EM01 | 24 | FA | E2 | 0-0 | SPARE | D06200J | A01 | \$D | *1 | GD00155 | S.. | 2 | | ALL | |
| EM02 | 24 | FA | E2 | 0-0 | 21-65-11 | D06200J | A02 | \$D | *1 | D00883B | E10 | | | ALL | |
| EM03 | 24 | FA | E2 | 0-0 | 21-31-11 | D06200J | A03 | \$D | *1 | D00883E | F14 | | | ALL | |
| EM04 | 24 | FA | E2 | 0-0 | 28-41-13 | D06200J | A04 | \$D | *1 | D00883E | D03 | | | ALL | |
| EM05 | 24 | FA | E2 | 0-0 | 80-11-11 | D06200J | A05 | \$D | *1 | D00883F | D09 | | | ALL | |
| EM06 | 24 | FA | E2 | 0-0 | 80-11-11 | D06200J | A06 | \$D | *1 | D00883B | H11 | | | ALL | |
| EM07 | 24 | FA | E2 | 0-0 | 28-42-12 | D06200J | A07 | \$D | *1 | D00883F | J09 | | | ALL | |

WIRE LIST

D280T132

91-21-11
Section W2000
Page 53
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| EM08 | 24 | FA | E2 | 0-0 | 21-65-11 | D06200J | A08 | \$D | *1 | D00883B | E11 | | | ALL | | |
| EM09 | 24 | FA | E2 | 0-0 | 21-65-11 | D06200J | A09 | \$D | *1 | D00883D | D05 | | | ALL | | |
| EM10 | 24 | FA | E2 | 0-0 | 21-65-11 | D06200J | A10 | \$D | *1 | D00883D | D04 | | | ALL | | |
| EM11 | 24 | FA | E2 | 0-0 | 36-11-11 | D06200J | A11 | \$D | *1 | D00883B | G11 | | | ALL | | |
| EM12 | 24 | FA | E2 | 0-0 | SPARE | D06200J | A12 | \$D | *1 | D00883A | REF | ** | | ALL | | |
| EM13 | 24 | FA | E2 | 0-0 | 21-64-11 | D06200J | A13 | \$D | *1 | TB0237X | C014 | BJ | | ALL | | |
| EM14 | 24 | FA | E2 | 0-0 | SPARE | D06200J | A14 | \$D | *1 | D00883A | REF | ** | | ALL | | |
| EM15 | 24 | FA | E2 | 0-0 | 21-33-11 | D06200J | A15 | \$D | *1 | D00883A | F13 | | | ALL | | |
| EM16 | 24 | FA | E2 | 0-0 | 74-31-11 | D06200J | A16 | \$D | *1 | D00883B | H15 | | | ALL | | |
| EM17 | 24 | FA | E2 | 0-0 | 24-51-42 | D06200J | A17 | \$D | *1 | D00883B | J14 | | | ALL | | |
| EM18 | 24 | FA | E2 | 0-0 | 24-11-11 | D06200J | A18 | \$D | *1 | D00883B | B05 | | | ALL | | |
| EM19 | 24 | FA | E2 | 0-0 | SPARE | D06200J | A19 | \$D | *1 | D00883A | REF | ** | | 050-099, 275-299 | | |
| EM19 | 24 | FA | E2 | 0-0 | SPARE | D06200J | A19 | \$D | *1 | D00883F | G02 | | | 150-199 | | |
| EM20 | 24 | FA | E2 | 0-0 | 99-99-99 | D06200J | A20 | \$D | *1 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| EM20 | 24 | FA | E2 | 0-0 | SPARE | D06200J | A20 | \$D | *1 | D00883A | REF | | | 155-199, 277-299 | | |
| FK01 | 24 | FA | F2 | 0-0 | SPARE | D06204J | A01 | \$D | *3 | GD00085 | S.. | 2 | *2 | ALL | | |
| FK02 | 24 | FA | F2 | 0-0 | 78-36-11 | D06204J | A02 | \$D | *3 | D00881B | H07 | | | ALL | | |
| FK03 | 24 | FA | F2 | 0-0 | 27-18-11 | D06204J | A03 | \$D | *3 | GD00089 | A.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| FK03 | 24 | FA | F2 | 0-0 | 27-18-11 | D06204J | A03 | \$D | *3 | GDX0002 | A.. | 2 | | 155-156, 165-166 | | |
| FK03 | 24 | FA | F2 | 0-0 | SPARE | D06204J | A03 | \$D | *3 | GDX0002 | A.. | 2 | | 157, 167-199, 277-299 | | |
| FK04 | 24 | FA | F2 | 0-0 | 27-18-11 | D06204J | A04 | \$D | *3 | D00881E | H03 | | | 050-099, 150-154, 162-165, 275-276 | | |
| FK04 | 24 | FA | F2 | 0-0 | SPARE | D06204J | A04 | \$D | *3 | D00881A | REF | ** | | 155-157, 166-199, 277-299 | | |
| FK05 | 24 | FA | F2 | 0-0 | 28-42-12 | D06204J | A05 | \$D | *3 | D00881D | G08 | | | ALL | | |
| FK06 | 24 | FA | F2 | 0-0 | 27-51-61 | D06204J | A06 | \$D | *3 | D00881D | F03 | | | ALL | | |
| FK07 | 24 | FA | F2 | 0-0 | 27-18-11 | D06204J | A07 | \$D | *3 | GD00089 | A.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| FK07 | 24 | FA | F2 | 0-0 | 27-18-11 | D06204J | A07 | \$D | *3 | GDX0002 | A.. | 2 | | 155-156, 165-166 | | |
| FK07 | 24 | FA | F2 | 0-0 | SPARE | D06204J | A07 | \$D | *3 | GDX0002 | A.. | 2 | | 157, 167-199, 277-299 | | |
| FK08 | 24 | FA | F2 | 0-0 | 27-18-11 | D06204J | A08 | \$D | *3 | D00881E | H05 | | | 050-099, 150-154, 162-165, 275-276 | | |
| FK08 | 24 | FA | F2 | 0-0 | SPARE | D06204J | A08 | \$D | *3 | D00881A | REF | ** | | 155-157, 166-199, 277-299 | | |
| FK09 | 24 | FA | F2 | 0-0 | 30-81-11 | D06204J | A09 | \$D | *3 | D00881E | D06 | | | 050-099, 150-199 | | |
| FK09 | 24 | FA | F2 | 0-0 | SPARE | D06204J | A09 | \$D | *3 | D00881A | REF | ** | | 275-299 | | |
| FK10 | 24 | FA | F2 | 0-0 | 30-81-11 | D06204J | A10 | \$D | *3 | D00881B | B13 | | | 050-099, 150-199 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 54

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| FK10 | 24 | FA | F2 | | 0-0 | SPARE | D06204J | A10 | \$D | *3 | D00881A | REF | ** | | 275-299 |
| FK11 | 24 | FA | F2 | | 0-0 | 28-42-11 | D06204J | A11 | \$D | *3 | D00881D | H03 | | | ALL |
| FK12 | 24 | FA | F2 | | 0-0 | 78-36-21 | D06204J | A12 | \$D | *3 | D00881D | J03 | | | ALL |
| FK13 | 24 | FA | F2 | | 0-0 | 26-18-11 | D06204J | A13 | \$D | *3 | D00881B | F04 | | | ALL |
| FK14 | 24 | FA | F2 | | 0-0 | 26-18-21 | D06204J | A14 | \$D | *3 | D00881D | G04 | | | ALL |
| FK15 | 24 | FA | F2 | | 0-0 | 26-18-31 | D06204J | A15 | \$D | *3 | D00881D | C02 | | | ALL |
| FK16 | 24 | FA | F2 | | 0-0 | SPARE | D06204J | A16 | \$D | *3 | D00881A | REF | ** | | ALL |
| FK17 | 24 | FA | F2 | | 0-0 | SPARE | D06204J | A17 | \$D | *3 | D00881A | REF | ** | | ALL |
| FK18 | 24 | FA | F2 | | 0-0 | 26-18-12 | D06204J | A18 | \$D | *3 | D00881D | H02 | | | ALL |
| FK19 | 24 | FA | F2 | | 0-0 | 28-31-12 | D06204J | A19 | \$D | * | D00881B | E08 | | | 050-099, 276 |
| FK19 | 24 | FA | F2 | | 0-0 | SPARE | D06204J | A19 | \$D | * | D00881A | REF | ** | | 150-154, 275 |
| FK19 | 24 | FA | F2 | | 0-0 | 28-31-12 | D06204J | A19 | \$D | *3 | D00881B | E08 | | | 155-199, 277-299 |
| FK20 | 24 | FA | F2 | | 0-0 | 99-99-99 | D06204J | A20 | \$D | *3 | D00881A | REF | | | 050-099, 150-154, 275-276 |
| FK20 | 24 | FA | F2 | | 0-0 | SPARE | D06204J | A20 | \$D | *3 | D00881A | REF | | | 155-199, 277-299 |
| FL01 | 24 | FB | F4 | | 0-0 | SPARE | D06204J | B01 | \$D | *3 | GD00085 | S.. | 2 | *2 | ALL |
| FL02 | 24 | FB | F4 | | 0-0 | 27-62-11 | D06204J | B02 | \$D | *3 | D00881A | G09 | | | ALL |
| FL03 | 24 | FB | F4 | | 0-0 | 30-31-21 | D06204J | B03 | \$D | *3 | D00881E | K12 | | | ALL |
| FL04 | 24 | FB | F4 | | 0-0 | 30-31-21 | D06204J | B04 | \$D | *3 | D00881E | A06 | | | ALL |
| FL05 | 24 | FB | F4 | | 0-0 | 30-31-23 | D06204J | B05 | \$D | *3 | D00881A | D01 | | | ALL |
| FL06 | 24 | FB | F4 | | 0-0 | 30-31-23 | D06204J | B06 | \$D | *3 | D00881E | K05 | | | ALL |
| FL07 | 24 | FB | F4 | | 0-0 | 30-32-21 | D06204J | B07 | \$D | *3 | D00881E | A07 | | | ALL |
| FL08 | 24 | FB | F4 | | 0-0 | SPARE | D06204J | B08 | \$D | *3 | D00881A | REF | ** | | ALL |
| FL09 | 24 | FB | F4 | | 0-0 | 76-11-11 | D06204J | B09 | \$D | *3 | D00881B | D14 | | | ALL |
| FL10 | 24 | FB | F4 | | 0-0 | SPARE | D06204J | B10 | \$D | *3 | D00881A | REF | ** | | ALL |
| FL11 | 24 | FB | F4 | | 0-0 | SPARE | D06204J | B11 | \$D | *3 | D00881A | REF | ** | | ALL |
| FL12 | 24 | FB | F4 | | 0-0 | SPARE | D06204J | B12 | \$D | *3 | D00881A | REF | ** | | ALL |
| FL13 | 24 | FB | F4 | | 0-0 | SPARE | D06204J | B13 | \$D | *3 | D00881A | REF | ** | | ALL |
| FL14 | 24 | FB | F4 | | 0-0 | SPARE | D06204J | B14 | \$D | *3 | D00881A | REF | ** | | ALL |
| FL15 | 24 | FB | F4 | | 0-0 | 29-11-22 | D06204J | B15 | \$D | *3 | D00881D | K13 | | | ALL |
| FL16 | 24 | FB | F4 | | 0-0 | 29-11-22 | D06204J | B16 | \$D | *3 | D00881F | C09 | | | ALL |
| FL17 | 24 | FB | F4 | | 0-0 | 28-42-13 | D06204J | B17 | \$D | * | D00881A | H02 | | | 050-099, 276 |
| FL17 | 24 | FB | F4 | | 0-0 | SPARE | D06204J | B17 | \$D | * | D00881A | REF | ** | | 150-154, 275 |
| FL17 | 24 | FB | F4 | | 0-0 | 28-42-13 | D06204J | B17 | \$D | *3 | D00881A | H02 | | | 155-199, 277-299 |
| FL18 | 24 | FB | F4 | | 0-0 | SPARE | D06204J | B18 | \$D | *3 | D00881A | REF | ** | | ALL |
| FL19 | 24 | FB | F4 | | 0-0 | SPARE | D06204J | B19 | \$D | *3 | D00881A | REF | ** | | ALL |
| FL20 | 24 | FB | F4 | | 0-0 | 99-99-99 | D06204J | B20 | \$D | *3 | D00881A | REF | | | 050-099, 150-154, 275-276 |
| FL20 | 24 | FB | F4 | | 0-0 | SPARE | D06204J | B20 | \$D | *3 | D00881A | REF | | | 155-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 55

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------------|--|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| FM01 | 24 | FA | F1 | 0-0 | 99-99-99 | D06204J | A01 | \$D | *3 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| FM01 | 24 | FA | F1 | 0-0 | SPARE | D06204J | A01 | \$D | *3 | D00883A | REF | | | 155-199, 277-299 | | |
| FM02 | 24 | FA | F1 | 0-0 | 78-36-11 | D06204J | A02 | \$D | *3 | D00883B | H07 | | | ALL | | |
| FM03 | 24 | FA | F1 | 0-0 | SPARE | D06204J | A03 | \$D | *3 | D00883A | REF | ** | | ALL | | |
| FM04 | 24 | FA | F1 | 0-0 | 27-18-11 | D06204J | A04 | \$D | *3 | D00883E | H03 | | | 050-099, 150-154, 162-165, 275-276 | | |
| FM04 | 24 | FA | F1 | 0-0 | SPARE | D06204J | A04 | \$D | *3 | D00883A | REF | ** | | 155-157, 166-199, 277-299 | | |
| FM05 | 24 | FA | F1 | 0-0 | 28-42-12 | D06204J | A05 | \$D | *3 | D00883D | G08 | | | ALL | | |
| FM06 | 24 | FA | F1 | 0-0 | 27-51-61 | D06204J | A06 | \$D | *3 | D00883D | F03 | | | ALL | | |
| FM07 | 24 | FA | F1 | 0-0 | SPARE | D06204J | A07 | \$D | *3 | D00883A | REF | ** | | ALL | | |
| FM08 | 24 | FA | F1 | 0-0 | 27-18-11 | D06204J | A08 | \$D | *3 | D00883E | H05 | | | 050-099, 150-154, 162-165, 275-276 | | |
| FM08 | 24 | FA | F1 | 0-0 | SPARE | D06204J | A08 | \$D | *3 | D00883A | REF | ** | | 155-157, 166-199, 277-299 | | |
| FM09 | 24 | FA | F1 | 0-0 | 30-81-11 | D06204J | A09 | \$D | *3 | D00883E | D06 | | | 050-099, 150-199 | | |
| FM09 | 24 | FA | F1 | 0-0 | SPARE | D06204J | A09 | \$D | *3 | D00883A | REF | ** | | 275-299 | | |
| FM10 | 24 | FA | F1 | 0-0 | 30-81-11 | D06204J | A10 | \$D | *3 | D00883B | B13 | | | 050-099, 150-199 | | |
| FM10 | 24 | FA | F1 | 0-0 | SPARE | D06204J | A10 | \$D | *3 | D00883A | REF | ** | | 275-299 | | |
| FM11 | 24 | FA | F1 | 0-0 | 28-42-11 | D06204J | A11 | \$D | *3 | D00883D | H03 | | | ALL | | |
| FM12 | 24 | FA | F1 | 0-0 | 78-36-21 | D06204J | A12 | \$D | *3 | D00883D | J03 | | | ALL | | |
| FM13 | 24 | FA | F1 | 0-0 | 26-18-11 | D06204J | A13 | \$D | *3 | D00883B | F04 | | | ALL | | |
| FM14 | 24 | FA | F1 | 0-0 | 26-18-21 | D06204J | A14 | \$D | *3 | D00883D | G04 | | | ALL | | |
| FM15 | 24 | FA | F1 | 0-0 | 26-18-31 | D06204J | A15 | \$D | *3 | D00883D | C02 | | | ALL | | |
| FM16 | 24 | FA | F1 | 0-0 | SPARE | D06204J | A16 | \$D | *3 | D00883A | REF | ** | | ALL | | |
| FM17 | 24 | FA | F1 | 0-0 | SPARE | D06204J | A17 | \$D | *3 | D00883A | REF | ** | | ALL | | |
| FM18 | 24 | FA | F1 | 0-0 | 26-18-12 | D06204J | A18 | \$D | *3 | D00883D | H02 | | | ALL | | |
| FM19 | 24 | FA | F1 | 0-0 | 28-31-12 | D06204J | A19 | \$D | * | D00883B | E08 | | | 050-099, 276 | | |
| FM19 | 24 | FA | F1 | 0-0 | SPARE | D06204J | A19 | \$D | * | D00883A | REF | ** | | 150-154, 275 | | |
| FM19 | 24 | FA | F1 | 0-0 | 28-31-12 | D06204J | A19 | \$D | *3 | D00883B | E08 | | | 155-199, 277-299 | | |
| FM20 | 24 | FA | F1 | 0-0 | 99-99-99 | D06204J | A20 | \$D | *3 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| FM20 | 24 | FA | F1 | 0-0 | SPARE | D06204J | A20 | \$D | *3 | D00883A | REF | | | 155-199, 277-299 | | |
| FN01 | 24 | FB | F3 | 0-0 | 99-99-99 | D06204J | B01 | \$D | *3 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| FN01 | 24 | FB | F3 | 0-0 | SPARE | D06204J | B01 | \$D | *3 | D00883A | REF | | | 155-199, 277-299 | | |
| FN02 | 24 | FB | F3 | 0-0 | 27-62-11 | D06204J | B02 | \$D | *3 | D00883A | G09 | | | ALL | | |
| FN03 | 24 | FB | F3 | 0-0 | 30-31-21 | D06204J | B03 | \$D | *3 | D00883E | K12 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 56

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|----------|---------|---------|-------|------|---------|--------|-------|------|------|---------------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| FN04 | 24 | FB | F3 | 0-0 | 30-31-21 | D06204J | B04 | \$D | *3 | D00883E | A06 | | | | ALL |
| FN05 | 24 | FB | F3 | 0-0 | 30-31-23 | D06204J | B05 | \$D | *3 | D00883A | D01 | | | | ALL |
| FN06 | 24 | FB | F3 | 0-0 | 30-31-23 | D06204J | B06 | \$D | *3 | D00883E | K05 | | | | ALL |
| FN07 | 24 | FB | F3 | 0-0 | 30-32-21 | D06204J | B07 | \$D | *3 | D00883E | A07 | | | | ALL |
| FN08 | 24 | FB | F3 | 0-0 | SPARE | D06204J | B08 | \$D | *3 | D00883A | REF | ** | | | ALL |
| FN09 | 24 | FB | F3 | 0-0 | 76-11-11 | D06204J | B09 | \$D | *3 | D00883B | D14 | | | | ALL |
| FN10 | 24 | FB | F3 | 0-0 | SPARE | D06204J | B10 | \$D | *3 | D00883A | REF | ** | | | ALL |
| FN11 | 24 | FB | F3 | 0-0 | SPARE | D06204J | B11 | \$D | *3 | D00883A | REF | ** | | | ALL |
| FN12 | 24 | FB | F3 | 0-0 | SPARE | D06204J | B12 | \$D | *3 | D00883A | REF | ** | | | ALL |
| FN13 | 24 | FB | F3 | 0-0 | SPARE | D06204J | B13 | \$D | *3 | D00883A | REF | ** | | | ALL |
| FN14 | 24 | FB | F3 | 0-0 | SPARE | D06204J | B14 | \$D | *3 | D00883A | REF | ** | | | ALL |
| FN15 | 24 | FB | F3 | 0-0 | 29-11-22 | D06204J | B15 | \$D | *3 | D00883D | K13 | | | | ALL |
| FN16 | 24 | FB | F3 | 0-0 | 29-11-22 | D06204J | B16 | \$D | *3 | D00883F | C09 | | | | ALL |
| FN17 | 24 | FB | F3 | 0-0 | 28-42-13 | D06204J | B17 | \$D | * | D00883A | H02 | | | | 050-099, 276 |
| FN17 | 24 | FB | F3 | 0-0 | SPARE | D06204J | B17 | \$D | * | D00883A | REF | ** | | | 150-154, 275 |
| FN17 | 24 | FB | F3 | 0-0 | 28-42-13 | D06204J | B17 | \$D | *3 | D00883A | H02 | | | | 155-199, 277-299 |
| FN18 | 24 | FB | F3 | 0-0 | SPARE | D06204J | B18 | \$D | *3 | D00883A | REF | ** | | | ALL |
| FN19 | 24 | FB | F3 | 0-0 | SPARE | D06204J | B19 | \$D | *3 | D00883A | REF | ** | | | ALL |
| FN20 | 24 | FB | F3 | 0-0 | 99-99-99 | D06204J | B20 | \$D | *3 | D00883A | REF | | | | 050-099, 150-154, 275-276 |
| FN20 | 24 | FB | F3 | 0-0 | SPARE | D06204J | B20 | \$D | *3 | D00883A | REF | | | | 155-199, 277-299 |
| HK01 | 24 | FA | H2 | 0-0 | SPARE | D06222J | A01 | \$D | *5 | GD00085 | S.. | 2 | | | ALL |
| HK02 | 24 | FA | H2 | 0-0 | 24-27-41 | D06222J | A02 | \$D | *5 | D00881D | C07 | | | | ALL |
| HK03 | 24 | FA | H2 | 0-0 | 24-28-11 | D06222J | A03 | \$D | *5 | D00881E | G08 | | | | ALL |
| HK04 | 24 | FA | H2 | 0-0 | 24-28-11 | D06222J | A04 | \$D | *5 | D00881E | G12 | | | | ALL |
| HK05 | 24 | FA | H2 | 0-0 | 49-71-11 | D06222J | A05 | \$D | *5 | D00881F | A05 | | | | ALL |
| HK06 | 24 | FA | H2 | 0-0 | SPARE | D06222J | A06 | \$D | *5 | D00881A | REF | ** | | | 050-099, 275-299 |
| HK06 | 24 | FA | H2 | 0-0 | SPARE | D06222J | A06 | \$D | *5 | D00881E | K04 | | | | 150-199 |
| HK07 | 24 | FA | H2 | 0-0 | 49-73-11 | D06222J | A07 | \$D | *5 | D00881F | A06 | | | | ALL |
| HK08 | 24 | FA | H2 | 0-0 | SPARE | D06222J | A08 | \$D | *5 | D00881A | REF | ** | | | ALL |
| HK09 | 24 | FA | H2 | 0-0 | 24-34-11 | D06222J | A09 | \$D | *5 | D00881F | A03 | | | | ALL |
| HK10 | 24 | FA | H2 | 0-0 | 24-34-11 | D06222J | A10 | \$D | *5 | D00881F | B02 | | | | ALL |
| HK11 | 24 | FA | H2 | 0-0 | 24-34-11 | D06222J | A11 | \$D | *5 | D00881F | B01 | | | | ALL |
| HK12 | 24 | FA | H2 | 0-0 | SPARE | D06222J | A12 | \$D | *5 | D00881A | REF | ** | | | ALL |
| HK13 | 24 | FA | H2 | 0-0 | 24-28-21 | D06222J | A13 | \$D | *5 | D00881E | E11 | | | | ALL |
| HK14 | 24 | FA | H2 | 0-0 | 24-28-21 | D06222J | A14 | \$D | *5 | D00881E | E12 | | | | ALL |
| HK15 | 24 | FA | H2 | 0-0 | 24-28-21 | D06222J | A15 | \$D | *5 | D00881E | E10 | | | | ALL |
| HK16 | 24 | FA | H2 | 0-0 | SPARE | D06222J | A16 | \$D | *5 | D00881A | REF | ** | | | ALL |
| HK17 | 24 | FA | H2 | 0-0 | SPARE | D06222J | A17 | \$D | *5 | D00881A | REF | ** | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W2000
 Page 57
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| HK18 | 24 | FA | H2 | 0-0 | SPARE | D06222J | A18 | \$D | *5 | D00881A | REF | ** | | ALL | | |
| HK19 | 24 | FA | H2 | 0-0 | SPARE | D06222J | A19 | \$D | *5 | D00881A | REF | ** | | 050-099, 150-199 | | |
| HK19 | 24 | FA | H2 | 0-0 | 26-22-21 | D06222J | A19 | \$D | *5 | D00881F | F09 | | | 275-299 | | |
| HK20 | 24 | FA | H2 | 0-0 | 99-99-99 | D06222J | A20 | \$D | *5 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| HK20 | 24 | FA | H2 | 0-0 | SPARE | D06222J | A20 | \$D | *5 | D00881A | REF | | | 155-199, 277-299 | | |
| HL01 | 24 | FB | H4 | 0-0 | SPARE | D06222J | B01 | \$D | *5 | GD00085 | S.. | 2 | | ALL | | |
| HL02 | 24 | FB | H4 | 0-0 | 26-21-11 | D06222J | B02 | \$D | *5 | D00881F | E03 | | | ALL | | |
| HL03 | 24 | FB | H4 | 0-0 | 26-16-21 | D06222J | B03 | \$D | *5 | D00881F | E07 | | | ALL | | |
| HL04 | 24 | FB | H4 | 0-0 | 28-25-21 | D06222J | B04 | \$D | *5 | D00881F | A10 | | | ALL | | |
| HL05 | 24 | FB | H4 | 0-0 | SPARE | D06222J | B05 | \$D | * | D00881A | CAP | Y | | 050-099, 150-154, 275-276 | | |
| HL05 | 24 | FB | H4 | 0-0 | SPARE | D06222J | B05 | \$D | *5 | D00881A | CAP | Y | | 155-199, 277-299 | | |
| HL06 | 24 | FB | H4 | 0-0 | SPARE | D06222J | B06 | \$D | *5 | D00881A | REF | ** | | ALL | | |
| HL07 | 24 | FB | H4 | 0-0 | 36-11-41 | D06222J | B07 | \$D | *5 | D00881F | F01 | | | ALL | | |
| HL08 | 24 | FB | H4 | 0-0 | 49-61-11 | D06222J | B08 | \$D | *5 | D00881F | B06 | | | ALL | | |
| HL09 | 24 | FB | H4 | 0-0 | 49-61-11 | D06222J | B09 | \$D | *5 | D00881B | A13 | | | ALL | | |
| HL10 | 24 | FB | H4 | 0-0 | 26-22-21 | D06222J | B10 | \$D | *5 | D00881D | C09 | | | 050-099, 150-199 | | |
| HL10 | 24 | FB | H4 | 0-0 | 26-22-21 | D06222J | B10 | \$D | *5 | D00881D | F02 | | | 275-299 | | |
| HL11 | 24 | FB | H4 | 0-0 | 26-23-11 | D06222J | B11 | \$D | *5 | D00881D | D01 | | | ALL | | |
| HL12 | 24 | FB | H4 | 0-0 | 49-15-11 | D06222J | B12 | \$D | *5 | D00881F | E01 | | | ALL | | |
| HL13 | 24 | FB | H4 | 0-0 | SPARE | D06222J | B13 | \$D | *5 | D00881A | REF | ** | | ALL | | |
| HL14 | 24 | FB | H4 | 0-0 | SPARE | D06222J | B14 | \$D | *5 | D00881A | REF | ** | | ALL | | |
| HL15 | 24 | FB | H4 | 0-0 | SPARE | D06222J | B15 | \$D | *5 | D00881A | REF | ** | | ALL | | |
| HL16 | 24 | FB | H4 | 0-0 | SPARE | D06222J | B16 | \$D | *5 | D00881A | REF | ** | | ALL | | |
| HL17 | 24 | FB | H4 | 0-0 | SPARE | D06222J | B17 | \$D | *5 | D00881A | REF | ** | | ALL | | |
| HL18 | 24 | FB | H4 | 0-0 | 31-41-35 | D06222J | B18 | \$D | *5 | D00881E | F02 | | | ALL | | |
| HL19 | 24 | FB | H4 | 0-0 | 31-41-35 | D06222J | B19 | \$D | *5 | D00881E | F01 | | | ALL | | |
| HL20 | 24 | FB | H4 | 0-0 | 99-99-99 | D06222J | B20 | \$D | *5 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| HL20 | 24 | FB | H4 | 0-0 | SPARE | D06222J | B20 | \$D | *5 | D00881A | REF | | | 155-199, 277-299 | | |
| HM01 | 24 | FA | H1 | 0-0 | 99-99-99 | D06222J | A01 | \$D | *5 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| HM01 | 24 | FA | H1 | 0-0 | SPARE | D06222J | A01 | \$D | *5 | D00883A | REF | | | 155-199, 277-299 | | |
| HM02 | 24 | FA | H1 | 0-0 | 24-27-41 | D06222J | A02 | \$D | *5 | D00883D | C07 | | | ALL | | |
| HM03 | 24 | FA | H1 | 0-0 | SPARE | D06222J | A03 | \$D | *5 | D00883A | REF | ** | | ALL | | |
| HM04 | 24 | FA | H1 | 0-0 | 24-28-11 | D06222J | A04 | \$D | *5 | D00883E | G12 | | | ALL | | |
| HM05 | 24 | FA | H1 | 0-0 | 49-71-11 | D06222J | A05 | \$D | *5 | TB0237R | C019 | 2 | | ALL | | |
| HM06 | 24 | FA | H1 | 0-0 | SPARE | D06222J | A06 | \$D | *5 | D00883A | REF | ** | | 050-099, 275-299 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 58

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| HM06 | 24 | FA | H1 | 0-0 | SPARE | D06222J | A06 | \$D | *5 | D00883E | K04 | | | 150-199 | | |
| HM07 | 24 | FA | H1 | 0-0 | 49-73-11 | D06222J | A07 | \$D | *5 | TB0237R | C020 | 2 | | ALL | | |
| HM08 | 24 | FA | H1 | 0-0 | SPARE | D06222J | A08 | \$D | *5 | D00883A | REF | ** | | ALL | | |
| HM09 | 24 | FA | H1 | 0-0 | SPARE | D06222J | A09 | \$D | *5 | D00883A | REF | ** | | ALL | | |
| HM10 | 24 | FA | H1 | 0-0 | 24-34-11 | D06222J | A10 | \$D | *5 | D00883F | B02 | | | ALL | | |
| HM11 | 24 | FA | H1 | 0-0 | 24-34-11 | D06222J | A11 | \$D | *5 | D00883F | B01 | | | ALL | | |
| HM12 | 24 | FA | H1 | 0-0 | SPARE | D06222J | A12 | \$D | *5 | D00883A | REF | ** | | ALL | | |
| HM13 | 24 | FA | H1 | 0-0 | 24-28-21 | D06222J | A13 | \$D | *5 | D00883E | E11 | | | ALL | | |
| HM14 | 24 | FA | H1 | 0-0 | 24-28-21 | D06222J | A14 | \$D | *5 | D00883E | E12 | | | ALL | | |
| HM15 | 24 | FA | H1 | 0-0 | 24-28-21 | D06222J | A15 | \$D | *5 | D00883E | E10 | | | ALL | | |
| HM16 | 24 | FA | H1 | 0-0 | SPARE | D06222J | A16 | \$D | *5 | D00883A | REF | ** | | ALL | | |
| HM17 | 24 | FA | H1 | 0-0 | SPARE | D06222J | A17 | \$D | *5 | D00883A | REF | ** | | ALL | | |
| HM18 | 24 | FA | H1 | 0-0 | SPARE | D06222J | A18 | \$D | *5 | D00883A | REF | ** | | ALL | | |
| HM19 | 24 | FA | H1 | 0-0 | SPARE | D06222J | A19 | \$D | *5 | D00883A | REF | ** | | 050-099, 150-199 | | |
| HM19 | 24 | FA | H1 | 0-0 | 26-22-21 | D06222J | A19 | \$D | *5 | D00883F | F09 | | | 275-299 | | |
| HM20 | 24 | FA | H1 | 0-0 | 99-99-99 | D06222J | A20 | \$D | *5 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| HM20 | 24 | FA | H1 | 0-0 | SPARE | D06222J | A20 | \$D | *5 | D00883A | REF | | | 155-199, 277-299 | | |
| HN01 | 24 | FB | H3 | 0-0 | 99-99-99 | D06222J | B01 | \$D | *5 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| HN01 | 24 | FB | H3 | 0-0 | SPARE | D06222J | B01 | \$D | *5 | D00883A | REF | | | 155-199, 277-299 | | |
| HN02 | 24 | FB | H3 | 0-0 | 26-21-11 | D06222J | B02 | \$D | *5 | D00883F | E03 | | | ALL | | |
| HN03 | 24 | FB | H3 | 0-0 | 26-16-21 | D06222J | B03 | \$D | *5 | D00883F | E07 | | | ALL | | |
| HN04 | 24 | FB | H3 | 0-0 | 28-25-21 | D06222J | B04 | \$D | *5 | D00883F | A10 | | | ALL | | |
| HN05 | 24 | FB | H3 | 0-0 | SPARE | D06222J | B05 | \$D | * | D00883A | CAP | Y | | 050-099, 150-154, 275-276 | | |
| HN05 | 24 | FB | H3 | 0-0 | SPARE | D06222J | B05 | \$D | *5 | D00883A | CAP | Y | | 155-199, 277-299 | | |
| HN06 | 24 | FB | H3 | 0-0 | SPARE | D06222J | B06 | \$D | *5 | D00883A | REF | ** | | ALL | | |
| HN07 | 24 | FB | H3 | 0-0 | 36-11-41 | D06222J | B07 | \$D | *5 | D00883F | F01 | | | ALL | | |
| HN08 | 24 | FB | H3 | 0-0 | 49-61-11 | D06222J | B08 | \$D | *5 | D00883F | B06 | | | ALL | | |
| HN09 | 24 | FB | H3 | 0-0 | 49-61-11 | D06222J | B09 | \$D | *5 | D00883B | A13 | | | ALL | | |
| HN10 | 24 | FB | H3 | 0-0 | 26-22-21 | D06222J | B10 | \$D | *5 | D00883D | C09 | | | 050-099, 150-199 | | |
| HN10 | 24 | FB | H3 | 0-0 | 26-22-21 | D06222J | B10 | \$D | *5 | D00883D | F02 | | | 275-299 | | |
| HN11 | 24 | FB | H3 | 0-0 | 26-23-11 | D06222J | B11 | \$D | *5 | D00883D | D01 | | | ALL | | |
| HN12 | 24 | FB | H3 | 0-0 | 49-15-11 | D06222J | B12 | \$D | *5 | D00883F | E01 | | | ALL | | |
| HN13 | 24 | FB | H3 | 0-0 | SPARE | D06222J | B13 | \$D | *5 | D00883A | REF | ** | | ALL | | |
| HN14 | 24 | FB | H3 | 0-0 | SPARE | D06222J | B14 | \$D | *5 | D00883D | REF | ** | | 050-099, 275-276 | | |
| HN14 | 24 | FB | H3 | 0-0 | SPARE | D06222J | B14 | \$D | *5 | D00883A | REF | ** | | 150-199, 277-299 | | |
| HN15 | 24 | FB | H3 | 0-0 | SPARE | D06222J | B15 | \$D | *5 | D00883A | REF | ** | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 59

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| HN16 | 24 | FB | H3 | | 0-0 | SPARE | D06222J | B16 | \$D | *5 | D00883A | REF | ** | | ALL |
| HN17 | 24 | FB | H3 | | 0-0 | SPARE | D06222J | B17 | \$D | *5 | D00883A | REF | ** | | ALL |
| HN18 | 24 | FB | H3 | | 0-0 | 31-41-35 | D06222J | B18 | \$D | *5 | D00883E | F02 | | | ALL |
| HN19 | 24 | FB | H3 | | 0-0 | 31-41-35 | D06222J | B19 | \$D | *5 | D00883E | F01 | | | ALL |
| HN20 | 24 | FB | H3 | | 0-0 | 99-99-99 | D06222J | B20 | \$D | *5 | D00883A | REF | | | 050-099, 150-154, 275-276 |
| HN20 | 24 | FB | H3 | | 0-0 | SPARE | D06222J | B20 | \$D | *5 | D00883A | REF | | | 155-199, 277-299 |
| LK01 | 24 | FA | L1 | | 0-0 | 99-99-99 | D06210J | A01 | \$D | *C | D00881A | REF | | | 050-099, 150-154, 275-276 |
| LK01 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A01 | \$D | * | D00881A | REF | | | 155-199, 277-299 |
| LK02 | 24 | FA | L1 | | 0-0 | 33-51-11 | D06210J | A02 | \$D | *C | D00881E | A11 | | | 050-099, 150-154, 275-276 |
| LK02 | 24 | FA | L1 | | 0-0 | 33-51-11 | D06210J | A02 | \$D | * | D00881E | A11 | | | 155-199, 277-299 |
| LK03 | 24 | FA | L1 | | 0-0 | 21-61-51 | D06210J | A03 | \$D | *C | D00881D | A13 | | | 050-099, 150-154, 275-276 |
| LK03 | 24 | FA | L1 | | 0-0 | 21-61-51 | D06210J | A03 | \$D | * | D00881D | A13 | | | 155-199, 277-299 |
| LK04 | 24 | FA | L1 | | 0-0 | 24-51-23 | D06210J | A04 | \$D | *C | D00881D | C08 | | | 050-099, 150-154, 275-276 |
| LK04 | 24 | FA | L1 | | 0-0 | 24-51-23 | D06210J | A04 | \$D | * | D00881D | C08 | | | 155-199, 277-299 |
| LK05 | 24 | FA | L1 | | 0-0 | 27-13-11 | D06210J | A05 | \$D | *C | D00881E | J02 | | | 050-099, 150-154, 275-276 |
| LK05 | 24 | FA | L1 | | 0-0 | 27-13-11 | D06210J | A05 | \$D | * | D00881E | J02 | | | 155-199, 277-299 |
| LK06 | 24 | FA | L1 | | 0-0 | 29-11-12 | D06210J | A06 | \$D | *C | D00881A | K11 | | | 050-099, 150-154, 275-276 |
| LK06 | 24 | FA | L1 | | 0-0 | 29-11-12 | D06210J | A06 | \$D | * | D00881A | K11 | | | 155-199, 277-299 |
| LK07 | 24 | FA | L1 | | 0-0 | 28-42-12 | D06210J | A07 | \$D | *C | D00881D | H06 | | | 050-099, 150-154, 275-276 |
| LK07 | 24 | FA | L1 | | 0-0 | 28-42-12 | D06210J | A07 | \$D | * | D00881D | H06 | | | 155-199, 277-299 |
| LK08 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A08 | \$D | *C | D00881A | REF | ** | | 050-099, 275-276 |
| LK08 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A08 | \$D | *C | D00881B | G04 | | | 150-154 |
| LK08 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A08 | \$D | * | D00881B | G04 | | | 155-199 |
| LK08 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A08 | \$D | * | D00881A | REF | ** | | 277-299 |
| LK09 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A09 | \$D | *C | D00881A | REF | ** | | 050-099, 275-276 |
| LK09 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A09 | \$D | *C | D00881E | G07 | | | 150-154 |
| LK09 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A09 | \$D | * | D00881E | G07 | | | 155-199 |
| LK09 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A09 | \$D | * | D00881A | REF | ** | | 277-299 |
| LK10 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A10 | \$D | *C | D00881A | REF | ** | | 050-099, 275-276 |
| LK10 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A10 | \$D | *C | D00881D | C10 | | | 150-154 |
| LK10 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A10 | \$D | * | D00881D | C10 | | | 155-199 |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 60

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| LK10 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A10 | \$D | * | D00881A | REF | ** | | 277-299 |
| LK11 | 24 | FA | L1 | | 0-0 | 36-11-21 | D06210J | A11 | \$D | *C | D00881B | G07 | | | 050-099, 150-154, 275-276 |
| LK11 | 24 | FA | L1 | | 0-0 | 36-11-21 | D06210J | A11 | \$D | * | D00881B | G07 | | | 155-199, 277-299 |
| LK12 | 24 | FA | L1 | | 0-0 | 21-26-21 | D06210J | A12 | \$D | *C | D00881A | E03 | | | 050-099, 150-154, 275-276 |
| LK12 | 24 | FA | L1 | | 0-0 | 21-26-21 | D06210J | A12 | \$D | * | D00881A | E03 | | | 155-199, 277-299 |
| LK13 | 24 | FA | L1 | | 0-0 | 21-65-11 | D06210J | A13 | \$D | *C | D00881D | D11 | | | 050-099, 150-154, 275-276 |
| LK13 | 24 | FA | L1 | | 0-0 | 21-65-11 | D06210J | A13 | \$D | * | D00881D | D11 | | | 155-199, 277-299 |
| LK14 | 24 | FA | L1 | | 0-0 | 21-65-11 | D06210J | A14 | \$D | *C | D00881D | D12 | | | 050-099, 150-154, 275-276 |
| LK14 | 24 | FA | L1 | | 0-0 | 21-65-11 | D06210J | A14 | \$D | * | D00881D | D12 | | | 155-199, 277-299 |
| LK15 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A15 | \$D | *C | D00881A | REF | ** | | 050-099, 150-154, 275-276 |
| LK15 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A15 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 |
| LK16 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A16 | \$D | * | D00881A | REF | ** | | ALL |
| LK17 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A17 | \$D | * | D00881A | REF | ** | | ALL |
| LK18 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A18 | \$D | * | D00881A | REF | ** | | ALL |
| LK19 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A19 | \$D | * | D00881A | REF | ** | | 050-099, 275-299 |
| LK19 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A19 | \$D | * | D00881F | J01 | | | 150-199 |
| LK20 | 24 | FA | L1 | | 0-0 | 99-99-99 | D06210J | A20 | \$D | * | D00881A | REF | | | 050-099, 150-154, 275-276 |
| LK20 | 24 | FA | L1 | | 0-0 | SPARE | D06210J | A20 | \$D | * | D00881A | REF | | | 155-199, 277-299 |
| LL01 | 24 | FB | L3 | | 0-0 | 99-99-99 | D06210J | B01 | \$D | *1 | D00881A | REF | | | 050-099, 150-154, 275-276 |
| LL01 | 24 | FB | L3 | | 0-0 | SPARE | D06210J | B01 | \$D | * | D00881A | REF | | | 155-199, 277-299 |
| LL02 | 24 | FB | L3 | | 0-0 | 24-51-43 | D06210J | B02 | \$D | *2 | D00881B | H14 | | | 050-099, 150-154, 275-276 |
| LL02 | 24 | FB | L3 | | 0-0 | 24-51-43 | D06210J | B02 | \$D | * | D00881B | H14 | | | 155-199, 277-299 |
| LL03 | 24 | FB | L3 | | 0-0 | 29-32-11 | D06210J | B03 | \$D | *3 | D00881B | K07 | | | 050-099, 150-154, 275-276 |
| LL03 | 24 | FB | L3 | | 0-0 | 29-32-11 | D06210J | B03 | \$D | * | D00881B | K07 | | | 155-199, 277-299 |
| LL04 | 24 | FB | L3 | | 0-0 | 29-32-11 | D06210J | B04 | \$D | *4 | D00881A | K03 | | | 050-099, 150-154, 275-276 |
| LL04 | 24 | FB | L3 | | 0-0 | 29-32-11 | D06210J | B04 | \$D | * | D00881A | K03 | | | 155-199, 277-299 |
| LL05 | 24 | FB | L3 | | 0-0 | 30-41-12 | D06210J | B05 | \$D | *5 | D00881E | C04 | | | 050-099, 150-154, 275-276 |
| LL05 | 24 | FB | L3 | | 0-0 | 30-41-12 | D06210J | B05 | \$D | * | D00881E | C04 | | | 155-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 61
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2002 | 286T2002 | | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | |
| LL06 | 24 | FB | L3 | 0-0 | 30-41-12 | D06210J | B06 | \$D | *6 | D00881E | C05 | | | 050-099, 150-154, 275-276 | |
| LL06 | 24 | FB | L3 | 0-0 | 30-41-12 | D06210J | B06 | \$D | * | D00881E | C05 | | | 155-199, 277-299 | |
| LL07 | 24 | FB | L3 | 0-0 | 29-11-31 | D06210J | B07 | \$D | *7 | D00881D | J11 | | | 050-099, 150-154, 275-276 | |
| LL07 | 24 | FB | L3 | 0-0 | 29-11-31 | D06210J | B07 | \$D | * | D00881D | J11 | | | 155-199, 277-299 | |
| LL08 | 24 | FB | L3 | 0-0 | SPARE | D06210J | B08 | \$D | *8 | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| LL08 | 24 | FB | L3 | 0-0 | SPARE | D06210J | B08 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | |
| LL09 | 24 | FB | L3 | 0-0 | 32-42-12 | D06210J | B09 | \$D | *9 | D00881A | G06 | | | 050-099, 150-154, 275-276 | |
| LL09 | 24 | FB | L3 | 0-0 | 32-42-12 | D06210J | B09 | \$D | * | D00881A | G06 | | | 155-199, 277-299 | |
| LL10 | 24 | FB | L3 | 0-0 | SPARE | D06210J | B10 | \$D | *A | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| LL10 | 24 | FB | L3 | 0-0 | SPARE | D06210J | B10 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | |
| LL11 | 24 | FB | L3 | 0-0 | SPARE | D06210J | B11 | \$D | *B | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| LL11 | 24 | FB | L3 | 0-0 | SPARE | D06210J | B11 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | |
| LL12 | 24 | FB | L3 | 0-0 | SPARE | D06210J | B12 | \$D | *C | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| LL12 | 24 | FB | L3 | 0-0 | SPARE | D06210J | B12 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | |
| LL13 | 24 | FB | L3 | 0-0 | SPARE | D06210J | B13 | \$D | *D | D00881A | REF | ** | | 050-099, 150-154, 275-276 | |
| LL13 | 24 | FB | L3 | 0-0 | SPARE | D06210J | B13 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 | |
| LL14 | 24 | FB | L3 | 0-0 | 30-21-11 | D06210J | B14 | \$D | *E | D00881E | A05 | | | 050-099, 150-154, 275-276 | |
| LL14 | 24 | FB | L3 | 0-0 | 30-21-11 | D06210J | B14 | \$D | * | D00881E | A05 | | | 155-199, 277-299 | |
| LL15 | 24 | FB | L3 | 0-0 | SPARE | D06210J | B15 | \$D | *F | D00881A | REF | ** | | 050-099, 150-154 | |
| LL15 | 24 | FB | L3 | 0-0 | SPARE | D06210J | B15 | \$D | * | D00881A | REF | ** | | 155-199 | |
| LL15 | 24 | FB | L3 | 0-0 | 30-21-11 | D06210J | B15 | \$D | *F | D00881D | J13 | | | 275-276 | |
| LL15 | 24 | FB | L3 | 0-0 | 30-21-11 | D06210J | B15 | \$D | * | D00881D | J13 | | | 277-299 | |
| LL16 | 24 | FB | L3 | 0-0 | 21-58-16 | D06210J | B16 | \$D | *G | D00881F | F05 | | | 050-099, 150-154, 275-276 | |
| LL16 | 24 | FB | L3 | 0-0 | 21-58-16 | D06210J | B16 | \$D | * | D00881F | F05 | | | 155-199, 277-299 | |
| LL17 | 24 | FB | L3 | 0-0 | 21-65-11 | D06210J | B17 | \$D | *H | D00881B | E11 | | | 050-099, 150-154, 275-276 | |
| LL17 | 24 | FB | L3 | 0-0 | 21-65-11 | D06210J | B17 | \$D | * | D00881B | E11 | | | 155-199, 277-299 | |
| LL18 | 24 | FB | L3 | 0-0 | 21-65-11 | D06210J | B18 | \$D | *I | D00881B | E10 | | | 050-099, 150-154, 275-276 | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 62

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| LL18 | 24 | FB | L3 | | 0-0 | 21-65-11 | D06210J | B18 | \$D | * | D00881B | E10 | | | 155-199, 277-299 |
| LL19 | 24 | FB | L3 | | 0-0 | SPARE | D06210J | B19 | \$D | *J | D00881A | REF | ** | | 050-099, 150-154, 275-276 |
| LL19 | 24 | FB | L3 | | 0-0 | SPARE | D06210J | B19 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 |
| LL20 | 24 | FB | L3 | | 0-0 | 99-99-99 | D06210J | B20 | \$D | *K | D00881A | REF | | | 050-099, 150-154, 275-276 |
| LL20 | 24 | FB | L3 | | 0-0 | SPARE | D06210J | B20 | \$D | * | D00881A | REF | | | 155-199, 277-299 |
| LM01 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A01 | \$D | *C | GD00157 | S.. | 2 | | 050-099, 150-154, 275-276 |
| LM01 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A01 | \$D | * | GD00157 | S.. | 2 | | 155-199, 277-299 |
| LM02 | 24 | FA | L2 | | 0-0 | 33-51-11 | D06210J | A02 | \$D | *C | D00883E | A11 | | | 050-099, 150-154, 275-276 |
| LM02 | 24 | FA | L2 | | 0-0 | 33-51-11 | D06210J | A02 | \$D | * | D00883E | A11 | | | 155-199, 277-299 |
| LM03 | 24 | FA | L2 | | 0-0 | 21-61-51 | D06210J | A03 | \$D | *C | D00883D | A13 | | | 050-099, 150-154, 275-276 |
| LM03 | 24 | FA | L2 | | 0-0 | 21-61-51 | D06210J | A03 | \$D | * | D00883D | A13 | | | 155-199, 277-299 |
| LM04 | 24 | FA | L2 | | 0-0 | 24-51-23 | D06210J | A04 | \$D | *C | D00883D | C08 | | | 050-099, 150-154, 275-276 |
| LM04 | 24 | FA | L2 | | 0-0 | 24-51-23 | D06210J | A04 | \$D | * | D00883D | C08 | | | 155-199, 277-299 |
| LM05 | 24 | FA | L2 | | 0-0 | 27-13-11 | D06210J | A05 | \$D | *C | D00883E | J02 | | | 050-099, 150-154, 275-276 |
| LM05 | 24 | FA | L2 | | 0-0 | 27-13-11 | D06210J | A05 | \$D | * | D00883E | J02 | | | 155-199, 277-299 |
| LM06 | 24 | FA | L2 | | 0-0 | 29-11-12 | D06210J | A06 | \$D | *C | D00883A | K11 | | | 050-099, 150-154, 275-276 |
| LM06 | 24 | FA | L2 | | 0-0 | 29-11-12 | D06210J | A06 | \$D | * | D00883A | K11 | | | 155-199, 277-299 |
| LM07 | 24 | FA | L2 | | 0-0 | 28-42-12 | D06210J | A07 | \$D | *C | D00883D | H06 | | | 050-099, 150-154, 275-276 |
| LM07 | 24 | FA | L2 | | 0-0 | 28-42-12 | D06210J | A07 | \$D | * | D00883D | H06 | | | 155-199, 277-299 |
| LM08 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A08 | \$D | *C | D00883A | REF | ** | | 050-099, 275-276 |
| LM08 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A08 | \$D | *C | D00883B | G04 | | | 150-154 |
| LM08 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A08 | \$D | * | D00883B | G04 | | | 155-199 |
| LM08 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A08 | \$D | * | D00883A | REF | ** | | 277-299 |
| LM09 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A09 | \$D | *C | D00883A | REF | ** | | 050-099, 275-276 |
| LM09 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A09 | \$D | *C | D00883E | G07 | | | 150-154 |
| LM09 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A09 | \$D | * | D00883E | G07 | | | 155-199 |
| LM09 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A09 | \$D | * | D00883A | REF | ** | | 277-299 |
| LM10 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A10 | \$D | *C | D00883A | REF | ** | | 050-099, 275-276 |
| LM10 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A10 | \$D | *C | D00883D | C10 | | | 150-154 |
| LM10 | 24 | FA | L2 | | 0-0 | SPARE | D06210J | A10 | \$D | * | D00883D | C10 | | | 155-199 |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 63
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|---------------------------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| LM10 | 24 | FA | L2 | 0-0 | SPARE | D06210J | A10 | \$D | * | D00883A | REF | ** | 277-299 | | |
| LM11 | 24 | FA | L2 | 0-0 | 36-11-21 | D06210J | A11 | \$D | *C | D00883B | G07 | | 050-099, 150-154, 275-276 | | |
| LM11 | 24 | FA | L2 | 0-0 | 36-11-21 | D06210J | A11 | \$D | * | D00883B | G07 | | 155-199, 277-299 | | |
| LM12 | 24 | FA | L2 | 0-0 | 21-26-21 | D06210J | A12 | \$D | *C | D00883A | E03 | | 050-099, 150-154, 275-276 | | |
| LM12 | 24 | FA | L2 | 0-0 | 21-26-21 | D06210J | A12 | \$D | * | D00883A | E03 | | 155-199, 277-299 | | |
| LM13 | 24 | FA | L2 | 0-0 | SPARE | D06210J | A13 | \$D | *C | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| LM13 | 24 | FA | L2 | 0-0 | SPARE | D06210J | A13 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| LM14 | 24 | FA | L2 | 0-0 | SPARE | D06210J | A14 | \$D | *C | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| LM14 | 24 | FA | L2 | 0-0 | SPARE | D06210J | A14 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| LM15 | 24 | FA | L2 | 0-0 | 21-65-11 | D06210J | A15 | \$D | *C | D00883D | D09 | | 050-099, 150-154, 275-276 | | |
| LM15 | 24 | FA | L2 | 0-0 | 21-65-11 | D06210J | A15 | \$D | * | D00883D | D09 | | 155-199, 277-299 | | |
| LM16 | 24 | FA | L2 | 0-0 | 21-65-11 | D06210J | A16 | \$D | * | D00883D | D10 | | ALL | | |
| LM17 | 24 | FA | L2 | 0-0 | 21-65-11 | D06210J | A17 | \$D | * | D00883D | D11 | | ALL | | |
| LM18 | 24 | FA | L2 | 0-0 | 21-65-11 | D06210J | A18 | \$D | * | D00883D | D12 | | ALL | | |
| LM19 | 24 | FA | L2 | 0-0 | SPARE | D06210J | A19 | \$D | * | D00883A | REF | ** | 050-099, 275-299 | | |
| LM19 | 24 | FA | L2 | 0-0 | SPARE | D06210J | A19 | \$D | * | D00883F | J01 | | 150-199 | | |
| LM20 | 24 | FA | L2 | 0-0 | 99-99-99 | D06210J | A20 | \$D | * | D00883A | REF | | 050-099, 150-154, 275-276 | | |
| LM20 | 24 | FA | L2 | 0-0 | SPARE | D06210J | A20 | \$D | * | D00883A | REF | | 155-199, 277-299 | | |
| LN01 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B01 | \$D | *1 | GD00157 | S.. | 2 | 050-099, 150-154, 275-276 | | |
| LN01 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B01 | \$D | * | GD00157 | S.. | 2 | 155-199, 277-299 | | |
| LN02 | 24 | FB | L4 | 0-0 | 24-51-43 | D06210J | B02 | \$D | *2 | D00883B | H14 | | 050-099, 150-154, 275-276 | | |
| LN02 | 24 | FB | L4 | 0-0 | 24-51-43 | D06210J | B02 | \$D | * | D00883B | H14 | | 155-199, 277-299 | | |
| LN03 | 24 | FB | L4 | 0-0 | 29-32-11 | D06210J | B03 | \$D | *3 | D00883B | K07 | | 050-099, 150-154, 275-276 | | |
| LN03 | 24 | FB | L4 | 0-0 | 29-32-11 | D06210J | B03 | \$D | * | D00883B | K07 | | 155-199, 277-299 | | |
| LN04 | 24 | FB | L4 | 0-0 | 29-32-11 | D06210J | B04 | \$D | *4 | D00883A | K03 | | 050-099, 150-154, 275-276 | | |
| LN04 | 24 | FB | L4 | 0-0 | 29-32-11 | D06210J | B04 | \$D | * | D00883A | K03 | | 155-199, 277-299 | | |
| LN05 | 24 | FB | L4 | 0-0 | 30-41-12 | D06210J | B05 | \$D | *5 | D00883E | C04 | | 050-099, 150-154, 275-276 | | |
| LN05 | 24 | FB | L4 | 0-0 | 30-41-12 | D06210J | B05 | \$D | * | D00883E | C04 | | 155-199, 277-299 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 64

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2002 | 286T2002 | | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | |
| LN06 | 24 | FB | L4 | 0-0 | 30-41-12 | D06210J | B06 | \$D | *6 | D00883E | C05 | | | 050-099, 150-154, 275-276 | |
| LN06 | 24 | FB | L4 | 0-0 | 30-41-12 | D06210J | B06 | \$D | * | D00883E | C05 | | | 155-199, 277-299 | |
| LN07 | 24 | FB | L4 | 0-0 | 29-11-31 | D06210J | B07 | \$D | *7 | D00883D | J11 | | | 050-099, 150-154, 275-276 | |
| LN07 | 24 | FB | L4 | 0-0 | 29-11-31 | D06210J | B07 | \$D | * | D00883D | J11 | | | 155-199, 277-299 | |
| LN08 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B08 | \$D | *8 | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| LN08 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B08 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| LN09 | 24 | FB | L4 | 0-0 | 32-42-12 | D06210J | B09 | \$D | *9 | D00883A | G06 | | | 050-099, 150-154, 275-276 | |
| LN09 | 24 | FB | L4 | 0-0 | 32-42-12 | D06210J | B09 | \$D | * | D00883A | G06 | | | 155-199, 277-299 | |
| LN10 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B10 | \$D | *A | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| LN10 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B10 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| LN11 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B11 | \$D | *B | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| LN11 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B11 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| LN12 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B12 | \$D | *C | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| LN12 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B12 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| LN13 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B13 | \$D | *D | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| LN13 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B13 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| LN14 | 24 | FB | L4 | 0-0 | 30-21-11 | D06210J | B14 | \$D | *E | D00883E | A05 | | | 050-099, 150-154, 275-276 | |
| LN14 | 24 | FB | L4 | 0-0 | 30-21-11 | D06210J | B14 | \$D | * | D00883E | A05 | | | 155-199, 277-299 | |
| LN15 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B15 | \$D | *F | D00883A | REF | ** | | 050-099, 150-154 | |
| LN15 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B15 | \$D | * | D00883A | REF | ** | | 155-199 | |
| LN15 | 24 | FB | L4 | 0-0 | 30-21-11 | D06210J | B15 | \$D | *F | D00883D | J13 | | | 275-276 | |
| LN15 | 24 | FB | L4 | 0-0 | 30-21-11 | D06210J | B15 | \$D | * | D00883D | J13 | | | 277-299 | |
| LN16 | 24 | FB | L4 | 0-0 | 21-58-16 | D06210J | B16 | \$D | *G | D00883F | F05 | | | 050-099, 150-154, 275-276 | |
| LN16 | 24 | FB | L4 | 0-0 | 21-58-16 | D06210J | B16 | \$D | * | D00883F | F05 | | | 155-199, 277-299 | |
| LN17 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B17 | \$D | *H | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |
| LN17 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B17 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 | |
| LN18 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B18 | \$D | *I | D00883A | REF | ** | | 050-099, 150-154, 275-276 | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 65
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------------------------------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| LN18 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B18 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | | |
| LN19 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B19 | \$D | *J | D00883A | REF | ** | 050-099, 150-154, 275-276 | | | |
| LN19 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B19 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | | |
| LN20 | 24 | FB | L4 | 0-0 | 99-99-99 | D06210J | B20 | \$D | *K | D00883A | REF | | 050-099, 150-154, 275-276 | | | |
| LN20 | 24 | FB | L4 | 0-0 | SPARE | D06210J | B20 | \$D | * | D00883A | REF | | 155-199, 277-299 | | | |
| MK01 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A01 | \$D | *B | GD00087 | S.. | 2 | 050-099, 150-154, 275-276 | | | |
| MK01 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A01 | \$D | * | GD00087 | S.. | 2 | 155-199, 277-299 | | | |
| MK02 | 24 | FA | M2 | 0-0 | 34-21-31 | D05061J | A02 | \$D | *B | D00881F | C03 | | 050-099, 150-154, 275-276 | | | |
| MK02 | 24 | FA | M2 | 0-0 | 34-21-31 | D05061J | A02 | \$D | * | D00881F | C03 | | 155-199, 277-299 | | | |
| MK03 | 24 | FA | M2 | 0-0 | 34-21-31 | D05061J | A03 | \$D | *B | D00881F | C04 | | 050-099, 150-154, 275-276 | | | |
| MK03 | 24 | FA | M2 | 0-0 | 34-21-31 | D05061J | A03 | \$D | * | D00881F | C04 | | 155-199, 277-299 | | | |
| MK04 | 24 | FA | M2 | 0-0 | 34-21-31 | D05061J | A04 | \$D | *B | D00881F | D05 | | 050-099, 150-154, 275-276 | | | |
| MK04 | 24 | FA | M2 | 0-0 | 34-21-31 | D05061J | A04 | \$D | * | D00881F | D05 | | 155-199, 277-299 | | | |
| MK05 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A05 | \$D | *B | D00881A | REF | ** | 050-099, 150-154, 275-276 | | | |
| MK05 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A05 | \$D | * | D00881A | REF | ** | 155-199, 277-299 | | | |
| MK06 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A06 | \$D | *B | D00881A | REF | ** | 050-099, 150-154, 275-276 | | | |
| MK06 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A06 | \$D | * | D00881A | REF | ** | 155-199, 277-299 | | | |
| MK07 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A07 | \$D | *B | D00881A | REF | ** | 050-099, 150-154, 275-276 | | | |
| MK07 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A07 | \$D | * | D00881A | REF | ** | 155-199, 277-299 | | | |
| MK08 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A08 | \$D | *B | D00881A | REF | ** | 050-099, 150-154, 275-276 | | | |
| MK08 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A08 | \$D | * | D00881A | REF | ** | 155-199, 277-299 | | | |
| MK09 | 24 | FA | M2 | 0-0 | 22-14-31 | D05061J | A09 | \$D | *B | D00881D | G07 | | 050-099, 150-154, 275-276 | | | |
| MK09 | 24 | FA | M2 | 0-0 | 22-14-31 | D05061J | A09 | \$D | * | D00881D | G07 | | 155-199, 277-299 | | | |
| MK10 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A10 | \$D | *B | D00881A | REF | ** | 050-099, 150-154, 275-276 | | | |
| MK10 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A10 | \$D | * | D00881A | REF | ** | 155-199, 277-299 | | | |
| MK11 | 24 | FA | M2 | 0-0 | SPARE | D05061J | A11 | \$D | *B | D00881A | REF | ** | 050-099, 150-154, 275-276 | | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 66

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| MK11 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A11 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 |
| MK12 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A12 | \$D | *B | D00881A | REF | ** | | 050-099, 150-154, 275-276 |
| MK12 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A12 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 |
| MK13 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A13 | \$D | *B | D00881A | REF | ** | | 050-099, 150-154, 275-276 |
| MK13 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A13 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 |
| MK14 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A14 | \$D | *B | D00881A | REF | ** | | 050-099, 150-154, 275-276 |
| MK14 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A14 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 |
| MK15 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A15 | \$D | *B | D00881A | REF | ** | | 050-099, 150-154, 275-276 |
| MK15 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A15 | \$D | * | D00881A | REF | ** | | 155-199, 277-299 |
| MK16 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A16 | \$D | * | D00881A | REF | ** | | ALL |
| MK17 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A17 | \$D | * | D00881A | REF | ** | | ALL |
| MK18 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A18 | \$D | * | D00881A | REF | ** | | ALL |
| MK19 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A19 | \$D | * | D00881A | REF | ** | | ALL |
| MK20 | 24 | FA | M2 | | 0-0 | 99-99-99 | D05061J | A20 | \$D | * | D00881A | REF | | | 050-099, 150-154, 275-276 |
| MK20 | 24 | FA | M2 | | 0-0 | SPARE | D05061J | A20 | \$D | * | D00881A | REF | | | 155-199, 277-299 |
| MM01 | 24 | FA | M1 | | 0-0 | 99-99-99 | D05061J | A01 | \$D | *B | D00883A | REF | | | 050-099, 150-154, 275-276 |
| MM01 | 24 | FA | M1 | | 0-0 | SPARE | D05061J | A01 | \$D | * | D00883A | REF | | | 155-199, 277-299 |
| MM02 | 24 | FA | M1 | | 0-0 | 34-21-31 | D05061J | A02 | \$D | *B | D00883F | C03 | | | 050-099, 150-154, 275-276 |
| MM02 | 24 | FA | M1 | | 0-0 | 34-21-31 | D05061J | A02 | \$D | * | D00883F | C03 | | | 155-199, 277-299 |
| MM03 | 24 | FA | M1 | | 0-0 | 34-21-31 | D05061J | A03 | \$D | *B | D00883F | C04 | | | 050-099, 150-154, 275-276 |
| MM03 | 24 | FA | M1 | | 0-0 | 34-21-31 | D05061J | A03 | \$D | * | D00883F | C04 | | | 155-199, 277-299 |
| MM04 | 24 | FA | M1 | | 0-0 | 34-21-31 | D05061J | A04 | \$D | *B | D00883F | D05 | | | 050-099, 150-154, 275-276 |
| MM04 | 24 | FA | M1 | | 0-0 | 34-21-31 | D05061J | A04 | \$D | * | D00883F | D05 | | | 155-199, 277-299 |
| MM05 | 24 | FA | M1 | | 0-0 | SPARE | D05061J | A05 | \$D | *B | D00883A | REF | ** | | 050-099, 150-154, 275-276 |
| MM05 | 24 | FA | M1 | | 0-0 | SPARE | D05061J | A05 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 |
| MM06 | 24 | FA | M1 | | 0-0 | SPARE | D05061J | A06 | \$D | *B | D00883A | REF | ** | | 050-099, 150-154, 275-276 |
| MM06 | 24 | FA | M1 | | 0-0 | SPARE | D05061J | A06 | \$D | * | D00883A | REF | ** | | 155-199, 277-299 |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 67
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|---|---------|-------|------|------|---------|-------|------|---------------------------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2002 | 286T2002 | | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | |
| MM07 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A07 | \$D | *B | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| MM07 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A07 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| MM08 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A08 | \$D | *B | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| MM08 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A08 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| MM09 | 24 | FA | M1 | 0-0 | 22-14-31 | D05061J | A09 | \$D | *B | D00883D | G07 | | 050-099, 150-154, 275-276 | | |
| MM09 | 24 | FA | M1 | 0-0 | 22-14-31 | D05061J | A09 | \$D | * | D00883D | G07 | | 155-199, 277-299 | | |
| MM10 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A10 | \$D | *B | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| MM10 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A10 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| MM11 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A11 | \$D | *B | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| MM11 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A11 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| MM12 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A12 | \$D | *B | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| MM12 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A12 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| MM13 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A13 | \$D | *B | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| MM13 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A13 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| MM14 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A14 | \$D | *B | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| MM14 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A14 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| MM15 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A15 | \$D | *B | D00883A | REF | ** | 050-099, 150-154, 275-276 | | |
| MM15 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A15 | \$D | * | D00883A | REF | ** | 155-199, 277-299 | | |
| MM16 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A16 | \$D | * | D00883A | REF | ** | ALL | | |
| MM17 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A17 | \$D | * | D00883A | REF | ** | ALL | | |
| MM18 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A18 | \$D | * | D00883A | REF | ** | ALL | | |
| MM19 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A19 | \$D | * | D00883A | REF | ** | ALL | | |
| MM20 | 24 | FA | M1 | 0-0 | 99-99-99 | D05061J | A20 | \$D | * | D00883A | REF | | 050-099, 150-154, 275-276 | | |
| MM20 | 24 | FA | M1 | 0-0 | SPARE | D05061J | A20 | \$D | * | D00883A | REF | | 155-199, 277-299 | | |
| NK01 | 24 | FA | N1 | 0-0 | 99-99-99 | D06220J | A01 | \$D | *7 | D00881A | REF | | 050-099, 150-154, 275-276 | | |
| NK01 | 24 | FA | N1 | 0-0 | SPARE | D06220J | A01 | \$D | *7 | D00881A | REF | | 155-199, 277-299 | | |
| NK02 | 24 | FA | N1 | 0-0 | 26-11-11 | D06220J | A02 | \$D | *7 | D00881E | G04 | | ALL | | |
| NK03 | 24 | FA | N1 | 0-0 | 26-11-12 | D06220J | A03 | \$D | *7 | D00881B | E06 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 68

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|----------|---------|---------|-------|------|---------|--------|-------|------|------|--|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| NK04 | 24 | FA | N1 | 0-0 | 26-11-21 | D06220J | A04 | \$D | *7 | D00881B | E09 | | | | ALL |
| NK05 | 24 | FA | N1 | 0-0 | 26-11-22 | D06220J | A05 | \$D | *7 | D00881E | G06 | | | | ALL |
| NK06 | 24 | FA | N1 | 0-0 | 26-15-11 | D06220J | A06 | \$D | *7 | D00881F | D04 | | | | ALL |
| NK07 | 24 | FA | N1 | 0-0 | 26-11-21 | D06220J | A07 | \$D | *7 | D00881D | G03 | | | | ALL |
| NK08 | 24 | FA | N1 | 0-0 | 26-11-22 | D06220J | A08 | \$D | *7 | D00881D | G05 | | | | ALL |
| NK09 | 24 | FA | N1 | 0-0 | 26-15-11 | D06220J | A09 | \$D | *7 | D00881F | F02 | | | | ALL |
| NK10 | 24 | FA | N1 | 0-0 | SPARE | D06220J | A10 | \$D | *7 | D00881A | REF | ** | | | ALL |
| NK11 | 24 | FA | N1 | 0-0 | SPARE | D06220J | A11 | \$D | *7 | D00881A | REF | ** | | | ALL |
| NK12 | 24 | FA | N1 | 0-0 | 26-16-11 | D06220J | A12 | \$D | *7 | D00881F | F07 | | | | ALL |
| NK13 | 24 | FA | N1 | 0-0 | 26-16-11 | D06220J | A13 | \$D | *7 | D00881B | G05 | | | | ALL |
| NK14 | 24 | FA | N1 | 0-0 | 26-16-11 | D06220J | A14 | \$D | *7 | D00881E | G02 | | | | ALL |
| NK15 | 24 | FA | N1 | 0-0 | 26-17-11 | D06220J | A15 | \$D | *7 | D00881D | B10 | | | | ALL |
| NK16 | 24 | FA | N1 | 0-0 | SPARE | D06220J | A16 | \$D | *7 | D00881A | REF | ** | | | ALL |
| NK17 | 24 | FA | N1 | 0-0 | SPARE | D06220J | A17 | \$D | *7 | D00881A | REF | ** | | | ALL |
| NK18 | 24 | FA | N1 | 0-0 | SPARE | D06220J | A18 | \$D | *7 | D00881A | REF | ** | | | ALL |
| NK19 | 24 | FA | N1 | 0-0 | SPARE | D06220J | A19 | \$D | *7 | D00881A | REF | ** | | | ALL |
| NK20 | 24 | FA | N1 | 0-0 | 99-99-99 | D06220J | A20 | \$D | *7 | D00881A | REF | | | | 050-099, 150-154, 275-276 155-199, 277-299 |
| NK20 | 24 | FA | N1 | 0-0 | SPARE | D06220J | A20 | \$D | *7 | D00881A | REF | | | | ALL |
| NM01 | 24 | FA | N2 | 0-0 | SPARE | D06220J | A01 | \$D | *7 | GD00157 | S.. | 2 | | | ALL |
| NM02 | 24 | FA | N2 | 0-0 | 26-11-11 | D06220J | A02 | \$D | *7 | D00883E | G04 | | | | ALL |
| NM03 | 24 | FA | N2 | 0-0 | 26-11-12 | D06220J | A03 | \$D | *7 | D00883B | E06 | | | | ALL |
| NM04 | 24 | FA | N2 | 0-0 | 26-11-21 | D06220J | A04 | \$D | *7 | D00883B | E09 | | | | ALL |
| NM05 | 24 | FA | N2 | 0-0 | 26-11-22 | D06220J | A05 | \$D | *7 | D00883E | G06 | | | | ALL |
| NM06 | 24 | FA | N2 | 0-0 | 26-15-11 | D06220J | A06 | \$D | *7 | D00883F | D04 | | | | ALL |
| NM07 | 24 | FA | N2 | 0-0 | 26-11-21 | D06220J | A07 | \$D | *7 | D00883D | G03 | | | | ALL |
| NM08 | 24 | FA | N2 | 0-0 | 26-11-22 | D06220J | A08 | \$D | *7 | D00883D | G05 | | | | ALL |
| NM09 | 24 | FA | N2 | 0-0 | 26-15-11 | D06220J | A09 | \$D | *7 | D00883F | F02 | | | | ALL |
| NM10 | 24 | FA | N2 | 0-0 | SPARE | D06220J | A10 | \$D | *7 | D00883A | REF | ** | | | ALL |
| NM11 | 24 | FA | N2 | 0-0 | SPARE | D06220J | A11 | \$D | *7 | D00883A | REF | ** | | | ALL |
| NM12 | 24 | FA | N2 | 0-0 | 26-16-11 | D06220J | A12 | \$D | *7 | D00883F | F07 | | | | ALL |
| NM13 | 24 | FA | N2 | 0-0 | 26-16-11 | D06220J | A13 | \$D | *7 | D00883B | G05 | | | | ALL |
| NM14 | 24 | FA | N2 | 0-0 | 26-16-11 | D06220J | A14 | \$D | *7 | D00883E | G02 | | | | ALL |
| NM15 | 24 | FA | N2 | 0-0 | 26-17-11 | D06220J | A15 | \$D | *7 | D00883D | B10 | | | | ALL |
| NM16 | 24 | FA | N2 | 0-0 | SPARE | D06220J | A16 | \$D | *7 | D00883A | REF | ** | | | ALL |
| NM17 | 24 | FA | N2 | 0-0 | SPARE | D06220J | A17 | \$D | *7 | D00883A | REF | ** | | | ALL |
| NM18 | 24 | FA | N2 | 0-0 | SPARE | D06220J | A18 | \$D | *7 | D00883A | REF | ** | | | ALL |
| NM19 | 24 | FA | N2 | 0-0 | SPARE | D06220J | A19 | \$D | *7 | D00883A | REF | ** | | | ALL |

WIRE LIST

D280T132

91-21-11
Section W2000
Page 69
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| NM20 | 24 | FA | N2 | 0-0 | 99-99-99 | D06220J | A20 | \$D | *7 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| NM20 | 24 | FA | N2 | 0-0 | SPARE | D06220J | A20 | \$D | *7 | D00883A | REF | | | 155-199, 277-299 | | |
| PK01 | 24 | FA | P2 | 0-0 | SPARE | D06216J | A01 | \$D | *9 | GD00087 | S.. | 2 | | ALL | | |
| PK02 | 24 | FA | P2 | 0-0 | SPARE | D06216J | A02 | \$D | *9 | D00881A | REF | ** | | ALL | | |
| PK03 | 24 | FA | P2 | 0-0 | 35-21-11 | D06216J | A03 | \$D | *9 | D00881F | F06 | | | ALL | | |
| PK04 | 24 | FA | P2 | 0-0 | 28-22-31 | D06216J | A04 | \$D | *9 | D00881E | C02 | | | ALL | | |
| PK05 | 24 | FA | P2 | 0-0 | 80-11-21 | D06216J | A05 | \$D | *9 | D00881F | B05 | | | ALL | | |
| PK06 | 24 | FA | P2 | 0-0 | 80-11-21 | D06216J | A06 | \$D | *9 | D00881D | K02 | | | ALL | | |
| PK07 | 24 | FA | P2 | 0-0 | 29-32-11 | D06216J | A07 | \$D | *9 | D00881F | E10 | | | ALL | | |
| PK08 | 24 | FA | P2 | 0-0 | 32-42-11 | D06216J | A08 | \$D | *9 | D00881F | H10 | | | ALL | | |
| PK09 | 24 | FA | P2 | 0-0 | 24-28-11 | D06216J | A09 | \$D | *9 | D00881E | G11 | | | ALL | | |
| PK10 | 24 | FA | P2 | 0-0 | 24-33-11 | D06216J | A10 | \$D | *9 | D00881A | D04 | | | ALL | | |
| PK11 | 24 | FA | P2 | 0-0 | 24-33-11 | D06216J | A11 | \$D | *9 | D00881D | B04 | | | ALL | | |
| PK12 | 24 | FA | P2 | 0-0 | SPARE | D06216J | A12 | \$D | *9 | D00881A | REF | ** | | ALL | | |
| PK13 | 24 | FA | P2 | 0-0 | SPARE | D06216J | A13 | \$D | *9 | D00881A | REF | ** | | ALL | | |
| PK14 | 24 | FA | P2 | 0-0 | SPARE | D06216J | A14 | \$D | *9 | D00881A | REF | ** | | 050-099, 275-299 | | |
| PK14 | 24 | FA | P2 | 0-0 | 73-14-11 | D06216J | A14 | \$D | *9 | D00881A | K07 | | | 150-199 | | |
| PK15 | 24 | FA | P2 | 0-0 | SPARE | D06216J | A15 | \$D | *9 | D00881A | REF | ** | | 050-099, 275-299 | | |
| PK15 | 24 | FA | P2 | 0-0 | 73-14-11 | D06216J | A15 | \$D | *9 | D00881D | F10 | | | 150-199 | | |
| PK16 | 24 | FA | P2 | 0-0 | 74-31-11 | D06216J | A16 | \$D | *9 | D00881B | K02 | | | ALL | | |
| PK17 | 24 | FA | P2 | 0-0 | SPARE | D06216J | A17 | \$D | *9 | D00881A | REF | ** | | ALL | | |
| PK18 | 24 | FA | P2 | 0-0 | 29-11-32 | D06216J | A18 | \$D | *9 | D00881A | K05 | | | ALL | | |
| PK19 | 24 | FA | P2 | 0-0 | SPARE | D06216J | A19 | \$D | *9 | D00881A | REF | ** | | ALL | | |
| PK20 | 24 | FA | P2 | 0-0 | 99-99-99 | D06216J | A20 | \$D | *9 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| PK20 | 24 | FA | P2 | 0-0 | SPARE | D06216J | A20 | \$D | *9 | D00881A | REF | | | 155-199, 277-299 | | |
| PL01 | 24 | FB | P4 | 0-0 | SPARE | D06216J | B01 | \$D | *9 | GD00087 | S.. | 2 | | ALL | | |
| PL02 | 24 | FB | P4 | 0-0 | 24-34-11 | D06216J | B02 | \$D | *9 | D00881B | D07 | | | ALL | | |
| PL03 | 24 | FB | P4 | 0-0 | 24-34-11 | D06216J | B03 | \$D | *9 | D00881B | D06 | | | ALL | | |
| PL04 | 24 | FB | P4 | 0-0 | 24-34-11 | D06216J | B04 | \$D | *9 | D00881B | D10 | | | ALL | | |
| PL05 | 24 | FB | P4 | 0-0 | 24-34-11 | D06216J | B05 | \$D | *9 | D00881B | D09 | | | ALL | | |
| PL06 | 24 | FB | P4 | 0-0 | 24-34-11 | D06216J | B06 | \$D | *9 | D00881B | D13 | | | ALL | | |
| PL07 | 24 | FB | P4 | 0-0 | 24-34-11 | D06216J | B07 | \$D | *9 | D00881B | D12 | | | ALL | | |
| PL08 | 24 | FB | P4 | 0-0 | 24-34-11 | D06216J | B08 | \$D | *9 | D00881E | G14 | | | ALL | | |
| PL09 | 24 | FB | P4 | 0-0 | 24-34-11 | D06216J | B09 | \$D | *9 | D00881B | E01 | | | ALL | | |
| PL10 | 24 | FB | P4 | 0-0 | 24-34-11 | D06216J | B10 | \$D | *9 | D00881F | A04 | | | ALL | | |
| PL11 | 24 | FB | P4 | 0-0 | 24-34-11 | D06216J | B11 | \$D | *9 | D00881E | A12 | | | ALL | | |
| PL12 | 24 | FB | P4 | 0-0 | 21-58-16 | D06216J | B12 | \$D | *9 | D00881B | G08 | | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 70

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| PL13 | 24 | FB | P4 | 0-0 | 24-34-11 | D06216J | B13 | \$D | *9 | D00881E | C15 | | | ALL | | |
| PL14 | 24 | FB | P4 | 0-0 | 24-34-11 | D06216J | B14 | \$D | *9 | D00881E | J14 | | | ALL | | |
| PL15 | 24 | FB | P4 | 0-0 | 35-11-13 | D06216J | B15 | \$D | *9 | D00881A | F09 | | | ALL | | |
| PL16 | 24 | FB | P4 | 0-0 | 35-11-13 | D06216J | B16 | \$D | *9 | D00881E | E06 | | | ALL | | |
| PL17 | 24 | FB | P4 | 0-0 | 49-94-14 | D06216J | B17 | \$D | *9 | D00881F | F10 | | | ALL | | |
| PL18 | 24 | FB | P4 | 0-0 | 49-94-14 | D06216J | B18 | \$D | *9 | GD00081 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| PL18 | 24 | FB | P4 | 0-0 | 49-94-14 | D06216J | B18 | \$D | *9 | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 | | |
| PL19 | 24 | FB | P4 | 0-0 | 49-94-14 | D06216J | B19 | \$D | *9 | TB0237Z | 18 | BJ | | ALL | | |
| PL20 | 24 | FB | P4 | 0-0 | 99-99-99 | D06216J | B20 | \$D | *9 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| PL20 | 24 | FB | P4 | 0-0 | SPARE | D06216J | B20 | \$D | *9 | D00881A | REF | | | 155-199, 277-299 | | |
| PM01 | 24 | FA | P1 | 0-0 | 99-99-99 | D06216J | A01 | \$D | *9 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| PM01 | 24 | FA | P1 | 0-0 | SPARE | D06216J | A01 | \$D | *9 | D00883A | REF | | | 155-199, 277-299 | | |
| PM02 | 24 | FA | P1 | 0-0 | SPARE | D06216J | A02 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| PM03 | 24 | FA | P1 | 0-0 | 35-21-11 | D06216J | A03 | \$D | *9 | D00883F | F06 | | | ALL | | |
| PM04 | 24 | FA | P1 | 0-0 | 28-22-31 | D06216J | A04 | \$D | *9 | D00883E | C02 | | | ALL | | |
| PM05 | 24 | FA | P1 | 0-0 | 80-11-21 | D06216J | A05 | \$D | *9 | D00883F | B05 | | | ALL | | |
| PM06 | 24 | FA | P1 | 0-0 | 80-11-21 | D06216J | A06 | \$D | *9 | D00883D | K02 | | | ALL | | |
| PM07 | 24 | FA | P1 | 0-0 | 29-32-11 | D06216J | A07 | \$D | *9 | D00883F | E10 | | | ALL | | |
| PM08 | 24 | FA | P1 | 0-0 | 32-42-11 | D06216J | A08 | \$D | *9 | D00883F | H10 | | | ALL | | |
| PM09 | 24 | FA | P1 | 0-0 | 24-28-11 | D06216J | A09 | \$D | *9 | D00883E | G11 | | | ALL | | |
| PM10 | 24 | FA | P1 | 0-0 | 24-33-11 | D06216J | A10 | \$D | *9 | D00883A | D04 | | | ALL | | |
| PM11 | 24 | FA | P1 | 0-0 | 24-33-11 | D06216J | A11 | \$D | *9 | D00883D | B04 | | | ALL | | |
| PM12 | 24 | FA | P1 | 0-0 | SPARE | D06216J | A12 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| PM13 | 24 | FA | P1 | 0-0 | SPARE | D06216J | A13 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| PM14 | 24 | FA | P1 | 0-0 | SPARE | D06216J | A14 | \$D | *9 | D00883A | REF | ** | | 050-099, 275-299 | | |
| PM14 | 24 | FA | P1 | 0-0 | 73-14-11 | D06216J | A14 | \$D | *9 | D00883A | K07 | | | 150-199 | | |
| PM15 | 24 | FA | P1 | 0-0 | SPARE | D06216J | A15 | \$D | *9 | D00883A | REF | ** | | 050-099, 275-299 | | |
| PM15 | 24 | FA | P1 | 0-0 | 73-14-11 | D06216J | A15 | \$D | *9 | D00883D | F10 | | | 150-199 | | |
| PM16 | 24 | FA | P1 | 0-0 | 74-31-11 | D06216J | A16 | \$D | *9 | D00883B | K02 | | | ALL | | |
| PM17 | 24 | FA | P1 | 0-0 | SPARE | D06216J | A17 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| PM18 | 24 | FA | P1 | 0-0 | 29-11-32 | D06216J | A18 | \$D | *9 | D00883A | K05 | | | ALL | | |
| PM19 | 24 | FA | P1 | 0-0 | SPARE | D06216J | A19 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| PM20 | 24 | FA | P1 | 0-0 | 99-99-99 | D06216J | A20 | \$D | *9 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| PM20 | 24 | FA | P1 | 0-0 | SPARE | D06216J | A20 | \$D | *9 | D00883A | REF | | | 155-199, 277-299 | | |

WIRE LIST

D280T132

91-21-11
Section W2000
Page 71
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| PN01 | 24 | FB | P3 | 0-0 | 99-99-99 | D06216J | B01 | \$D | *9 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| PN01 | 24 | FB | P3 | 0-0 | SPARE | D06216J | B01 | \$D | *9 | D00883A | REF | | | 155-199, 277-299 | | |
| PN02 | 24 | FB | P3 | 0-0 | 24-34-11 | D06216J | B02 | \$D | *9 | D00883B | D07 | | | ALL | | |
| PN03 | 24 | FB | P3 | 0-0 | 24-34-11 | D06216J | B03 | \$D | *9 | D00883B | D06 | | | ALL | | |
| PN04 | 24 | FB | P3 | 0-0 | 24-34-11 | D06216J | B04 | \$D | *9 | D00883B | D10 | | | ALL | | |
| PN05 | 24 | FB | P3 | 0-0 | 24-34-11 | D06216J | B05 | \$D | *9 | D00883B | D09 | | | ALL | | |
| PN06 | 24 | FB | P3 | 0-0 | 24-34-11 | D06216J | B06 | \$D | *9 | D00883B | D13 | | | ALL | | |
| PN07 | 24 | FB | P3 | 0-0 | 24-34-11 | D06216J | B07 | \$D | *9 | D00883B | D12 | | | ALL | | |
| PN08 | 24 | FB | P3 | 0-0 | 24-34-11 | D06216J | B08 | \$D | *9 | D00883E | G14 | | | ALL | | |
| PN09 | 24 | FB | P3 | 0-0 | 24-34-11 | D06216J | B09 | \$D | *9 | D00883B | E01 | | | ALL | | |
| PN10 | 24 | FB | P3 | 0-0 | 24-34-11 | D06216J | B10 | \$D | *9 | D00883F | A04 | | | ALL | | |
| PN11 | 24 | FB | P3 | 0-0 | 24-34-11 | D06216J | B11 | \$D | *9 | D00883E | A12 | | | ALL | | |
| PN12 | 24 | FB | P3 | 0-0 | 21-58-16 | D06216J | B12 | \$D | *9 | D00883B | G08 | | | ALL | | |
| PN13 | 24 | FB | P3 | 0-0 | 24-34-11 | D06216J | B13 | \$D | *9 | D00883E | C15 | | | ALL | | |
| PN14 | 24 | FB | P3 | 0-0 | 24-34-11 | D06216J | B14 | \$D | *9 | D00883E | J14 | | | ALL | | |
| PN15 | 24 | FB | P3 | 0-0 | 35-11-13 | D06216J | B15 | \$D | *9 | D00883A | F09 | | | ALL | | |
| PN16 | 24 | FB | P3 | 0-0 | 35-11-13 | D06216J | B16 | \$D | *9 | D00883E | E06 | | | ALL | | |
| PN17 | 24 | FB | P3 | 0-0 | 49-94-14 | D06216J | B17 | \$D | *9 | D00883F | F10 | | | ALL | | |
| PN18 | 24 | FB | P3 | 0-0 | SPARE | D06216J | B18 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| PN19 | 24 | FB | P3 | 0-0 | SPARE | D06216J | B19 | \$D | *9 | D00883A | REF | ** | | ALL | | |
| PN20 | 24 | FB | P3 | 0-0 | 99-99-99 | D06216J | B20 | \$D | *9 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| PN20 | 24 | FB | P3 | 0-0 | SPARE | D06216J | B20 | \$D | *9 | D00883A | REF | | | 155-199, 277-299 | | |
| QK01 | 24 | FA | Q1 | 0-0 | 99-99-99 | D06218J | A01 | \$D | *2 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| QK01 | 24 | FA | Q1 | 0-0 | SPARE | D06218J | A01 | \$D | *2 | D00881A | REF | | | 155-199, 277-299 | | |
| QK02 | 24 | FA | Q1 | 0-0 | 26-11-11 | D06218J | A02 | \$D | *2 | D00881D | G06 | | | ALL | | |
| QK03 | 24 | FA | Q1 | 0-0 | 26-11-12 | D06218J | A03 | \$D | *2 | D00881A | G04 | | | ALL | | |
| QK04 | 24 | FA | Q1 | 0-0 | 26-11-21 | D06218J | A04 | \$D | *2 | D00881A | G02 | | | ALL | | |
| QK05 | 24 | FA | Q1 | 0-0 | 26-11-22 | D06218J | A05 | \$D | *2 | D00881D | G09 | | | ALL | | |
| QK06 | 24 | FA | Q1 | 0-0 | 26-15-11 | D06218J | A06 | \$D | *2 | D00881D | F04 | | | ALL | | |
| QK07 | 24 | FA | Q1 | 0-0 | 26-11-11 | D06218J | A07 | \$D | *2 | D00881B | E04 | | | ALL | | |
| QK08 | 24 | FA | Q1 | 0-0 | 26-11-12 | D06218J | A08 | \$D | *2 | D00881B | E05 | | | ALL | | |
| QK09 | 24 | FA | Q1 | 0-0 | SPARE | D06218J | A09 | \$D | *2 | D00881A | REF | ** | | ALL | | |
| QK10 | 24 | FA | Q1 | 0-0 | 26-11-11 | D06218J | A10 | \$D | *2 | D00881E | A02 | | | ALL | | |
| QK11 | 24 | FA | Q1 | 0-0 | 77-12-11 | D06218J | A11 | \$D | *2 | D00881B | D01 | | | ALL | | |
| QK12 | 24 | FA | Q1 | 0-0 | 77-12-11 | D06218J | A12 | \$D | *2 | D00881B | D02 | | | ALL | | |
| QK13 | 24 | FA | Q1 | 0-0 | SPARE | D06218J | A13 | \$D | *2 | D00881A | REF | ** | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 72

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| QK14 | 24 | FA | Q1 | 0-0 | 28-22-31 | D06218J | A14 | \$D | *2 | D00881F | H04 | | | ALL | | |
| QK15 | 24 | FA | Q1 | 0-0 | 27-23-11 | D06218J | A15 | \$D | *2 | D00881A | H01 | | | ALL | | |
| QK16 | 24 | FA | Q1 | 0-0 | 28-42-21 | D06218J | A16 | \$D | *2 | D00881F | D10 | | | ALL | | |
| QK17 | 24 | FA | Q1 | 0-0 | 31-31-13 | D06218J | A17 | \$D | *2 | D00881A | J14 | | | ALL | | |
| QK18 | 24 | FA | Q1 | 0-0 | 29-11-32 | D06218J | A18 | \$D | *2 | D00881D | J10 | | | ALL | | |
| QK19 | 24 | FA | Q1 | 0-0 | 32-41-11 | D06218J | A19 | \$D | *2 | D00881E | H12 | | | ALL | | |
| QK20 | 24 | FA | Q1 | 0-0 | 99-99-99 | D06218J | A20 | \$D | *2 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| QK20 | 24 | FA | Q1 | 0-0 | SPARE | D06218J | A20 | \$D | *2 | D00881A | REF | | | 155-199, 277-299 | | |
| QL01 | 24 | FB | Q3 | 0-0 | 99-99-99 | D06218J | B01 | \$D | *2 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| QL01 | 24 | FB | Q3 | 0-0 | SPARE | D06218J | B01 | \$D | *2 | D00881A | REF | | | 155-199, 277-299 | | |
| QL02 | 24 | FB | Q3 | 0-0 | 26-21-11 | D06218J | B02 | \$D | *2 | D00881D | G02 | | | ALL | | |
| QL03 | 24 | FB | Q3 | 0-0 | 26-23-12 | D06218J | B03 | \$D | *2 | D00881F | C08 | | | ALL | | |
| QL04 | 24 | FB | Q3 | 0-0 | 29-21-31 | D06218J | B04 | \$D | *2 | D00881F | K06 | | | ALL | | |
| QL05 | 24 | FB | Q3 | 0-0 | 73-21-14 | D06218J | B05 | \$D | *2 | GD00083 | S.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| QL05 | 24 | FB | Q3 | 0-0 | 73-21-14 | D06218J | B05 | \$D | *2 | GDX0002 | S.. | 2 | | 155-157, 165-199, 277-299 | | |
| QL06 | 24 | FB | Q3 | 0-0 | 76-11-11 | D06218J | B06 | \$D | *2 | D00881B | J03 | | | ALL | | |
| QL07 | 24 | FB | Q3 | 0-0 | 76-11-11 | D06218J | B07 | \$D | *2 | D00881B | D15 | | | ALL | | |
| QL08 | 24 | FB | Q3 | 0-0 | 26-16-21 | D06218J | B08 | \$D | *2 | D00881D | G11 | | | ALL | | |
| QL09 | 24 | FB | Q3 | 0-0 | 26-16-21 | D06218J | B09 | \$D | *2 | D00881E | C11 | | | ALL | | |
| QL10 | 24 | FB | Q3 | 0-0 | 32-42-11 | D06218J | B10 | \$D | *2 | D00881B | F15 | | | ALL | | |
| QL11 | 24 | FB | Q3 | 0-0 | 32-42-11 | D06218J | B11 | \$D | *2 | D00881A | D03 | | | ALL | | |
| QL12 | 24 | FB | Q3 | 0-0 | 32-44-11 | D06218J | B12 | \$D | *2 | D00881A | G03 | | | ALL | | |
| QL13 | 24 | FB | Q3 | 0-0 | 32-42-11 | D06218J | B13 | \$D | *2 | D00881D | B12 | | | ALL | | |
| QL14 | 24 | FB | Q3 | 0-0 | 73-21-14 | D06218J | B14 | \$D | *2 | D00881A | J04 | | | ALL | | |
| QL15 | 24 | FB | Q3 | 0-0 | 73-21-14 | D06218J | B15 | \$D | *2 | D00881A | J03 | | | ALL | | |
| QL16 | 24 | FB | Q3 | 0-0 | 26-16-11 | D06218J | B16 | \$D | *2 | D00881D | F07 | | | ALL | | |
| QL17 | 24 | FB | Q3 | 0-0 | 26-16-11 | D06218J | B17 | \$D | *2 | D00881A | H06 | | | ALL | | |
| QL18 | 24 | FB | Q3 | 0-0 | 26-16-11 | D06218J | B18 | \$D | *2 | D00881D | F01 | | | ALL | | |
| QL19 | 24 | FB | Q3 | 0-0 | SPARE | D06218J | B19 | \$D | *2 | D00881A | REF | ** | | ALL | | |
| QL20 | 24 | FB | Q3 | 0-0 | 99-99-99 | D06218J | B20 | \$D | *2 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| QL20 | 24 | FB | Q3 | 0-0 | SPARE | D06218J | B20 | \$D | *2 | D00881A | REF | | | 155-199, 277-299 | | |
| QM01 | 24 | FA | Q2 | 0-0 | SPARE | D06218J | A01 | \$D | *2 | GD00157 | S.. | 2 | | ALL | | |
| QM02 | 24 | FA | Q2 | 0-0 | 26-11-11 | D06218J | A02 | \$D | *2 | D00883D | G06 | | | ALL | | |
| QM03 | 24 | FA | Q2 | 0-0 | 26-11-12 | D06218J | A03 | \$D | *2 | D00883A | G04 | | | ALL | | |

WIRE LIST

D280T132

91-21-11
Section W2000
Page 73
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|---|----------|---------|---------|-------|------|---------|--------|-------|------|------|--|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | |
| QM04 | 24 | FA | Q2 | 0-0 | 26-11-21 | D06218J | A04 | \$D | *2 | D00883A | G02 | | | | ALL |
| QM05 | 24 | FA | Q2 | 0-0 | 26-11-22 | D06218J | A05 | \$D | *2 | D00883D | G09 | | | | ALL |
| QM06 | 24 | FA | Q2 | 0-0 | 26-15-11 | D06218J | A06 | \$D | *2 | D00883D | F04 | | | | ALL |
| QM07 | 24 | FA | Q2 | 0-0 | 26-11-11 | D06218J | A07 | \$D | *2 | D00883B | E04 | | | | ALL |
| QM08 | 24 | FA | Q2 | 0-0 | 26-11-12 | D06218J | A08 | \$D | *2 | D00883B | E05 | | | | ALL |
| QM09 | 24 | FA | Q2 | 0-0 | SPARE | D06218J | A09 | \$D | *2 | D00883A | REF | ** | | | ALL |
| QM10 | 24 | FA | Q2 | 0-0 | 26-11-11 | D06218J | A10 | \$D | *2 | D00883E | A02 | | | | ALL |
| QM11 | 24 | FA | Q2 | 0-0 | 77-12-11 | D06218J | A11 | \$D | *2 | D00883B | D01 | | | | ALL |
| QM12 | 24 | FA | Q2 | 0-0 | 77-12-11 | D06218J | A12 | \$D | *2 | D00883B | D02 | | | | ALL |
| QM13 | 24 | FA | Q2 | 0-0 | 77-12-11 | D06218J | A13 | \$D | *2 | GD00157 | S.. | 2 | | | ALL |
| QM14 | 24 | FA | Q2 | 0-0 | 28-22-31 | D06218J | A14 | \$D | *2 | D00883F | H04 | | | | ALL |
| QM15 | 24 | FA | Q2 | 0-0 | 27-23-11 | D06218J | A15 | \$D | *2 | D00883A | H01 | | | | ALL |
| QM16 | 24 | FA | Q2 | 0-0 | 28-42-21 | D06218J | A16 | \$D | *2 | D00883F | D10 | | | | ALL |
| QM17 | 24 | FA | Q2 | 0-0 | 31-31-13 | D06218J | A17 | \$D | *2 | D00883A | J14 | | | | ALL |
| QM18 | 24 | FA | Q2 | 0-0 | 29-11-32 | D06218J | A18 | \$D | *2 | D00883D | J10 | | | | ALL |
| QM19 | 24 | FA | Q2 | 0-0 | 32-41-11 | D06218J | A19 | \$D | *2 | D00883E | H12 | | | | ALL |
| QM20 | 24 | FA | Q2 | 0-0 | 99-99-99 | D06218J | A20 | \$D | *2 | D00883A | REF | | | | 050-099, 150-154, 275-276 155-199, 277-299 |
| QM20 | 24 | FA | Q2 | 0-0 | SPARE | D06218J | A20 | \$D | *2 | D00883A | REF | | | | 155-199, 277-299 |
| QN01 | 24 | FB | Q4 | 0-0 | SPARE | D06218J | B01 | \$D | *2 | GD00157 | S.. | 2 | | | ALL |
| QN02 | 24 | FB | Q4 | 0-0 | 26-21-11 | D06218J | B02 | \$D | *2 | D00883D | G02 | | | | ALL |
| QN03 | 24 | FB | Q4 | 0-0 | 26-23-12 | D06218J | B03 | \$D | *2 | D00883F | C08 | | | | ALL |
| QN04 | 24 | FB | Q4 | 0-0 | 29-21-31 | D06218J | B04 | \$D | *2 | D00883F | K06 | | | | ALL |
| QN05 | 24 | FB | Q4 | 0-0 | SPARE | D06218J | B05 | \$D | *2 | D00883A | REF | ** | | | ALL |
| QN06 | 24 | FB | Q4 | 0-0 | 76-11-11 | D06218J | B06 | \$D | *2 | D00883B | J03 | | | | ALL |
| QN07 | 24 | FB | Q4 | 0-0 | 76-11-11 | D06218J | B07 | \$D | *2 | D00883B | D15 | | | | ALL |
| QN08 | 24 | FB | Q4 | 0-0 | 26-16-21 | D06218J | B08 | \$D | *2 | D00883D | G11 | | | | ALL |
| QN09 | 24 | FB | Q4 | 0-0 | 26-16-21 | D06218J | B09 | \$D | *2 | D00883E | C11 | | | | ALL |
| QN10 | 24 | FB | Q4 | 0-0 | 32-42-11 | D06218J | B10 | \$D | *2 | D00883B | F15 | | | | ALL |
| QN11 | 24 | FB | Q4 | 0-0 | 32-42-11 | D06218J | B11 | \$D | *2 | D00883A | D03 | | | | ALL |
| QN12 | 24 | FB | Q4 | 0-0 | 32-44-11 | D06218J | B12 | \$D | *2 | D00883A | G03 | | | | ALL |
| QN13 | 24 | FB | Q4 | 0-0 | 32-42-11 | D06218J | B13 | \$D | *2 | D00883D | B12 | | | | ALL |
| QN14 | 24 | FB | Q4 | 0-0 | 73-21-14 | D06218J | B14 | \$D | *2 | D00883A | J04 | | | | ALL |
| QN15 | 24 | FB | Q4 | 0-0 | 73-21-14 | D06218J | B15 | \$D | *2 | D00883A | J03 | | | | ALL |
| QN16 | 24 | FB | Q4 | 0-0 | 26-16-11 | D06218J | B16 | \$D | *2 | D00883D | F07 | | | | ALL |
| QN17 | 24 | FB | Q4 | 0-0 | 26-16-11 | D06218J | B17 | \$D | *2 | D00883A | H06 | | | | ALL |
| QN18 | 24 | FB | Q4 | 0-0 | 26-16-11 | D06218J | B18 | \$D | *2 | D00883D | F01 | | | | ALL |
| QN19 | 24 | FB | Q4 | 0-0 | SPARE | D06218J | B19 | \$D | *2 | D00883A | REF | ** | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 74

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| QN20 | 24 | FB | Q4 | 0-0 | 99-99-99 | D06218J | B20 | \$D | *2 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| QN20 | 24 | FB | Q4 | 0-0 | SPARE | D06218J | B20 | \$D | *2 | D00883A | REF | | | 155-199, 277-299 | | |
| RK01 | 24 | FA | R2 | 0-0 | SPARE | D05051J | A01 | \$D | *4 | GD00087 | S.. | 2 | | ALL | | |
| RK02 | 24 | FA | R2 | 0-0 | 22-21-11 | D05051J | A02 | \$D | *4 | D00881D | A06 | | | ALL | | |
| RK03 | 24 | FA | R2 | 0-0 | SPARE | D05051J | A03 | \$D | *4 | D00881A | REF | ** | | ALL | | |
| RK04 | 24 | FA | R2 | 0-0 | 27-09-14 | D05051J | A04 | \$D | *4 | D00881F | D03 | | | ALL | | |
| RK05 | 24 | FA | R2 | 0-0 | 27-09-14 | D05051J | A05 | \$D | *4 | D00881E | A10 | | | ALL | | |
| RK06 | 24 | FA | R2 | 0-0 | 27-11-12 | D05051J | A06 | \$D | *4 | D00881D | C03 | | | ALL | | |
| RK07 | 24 | FA | R2 | 0-0 | 27-41-11 | D05051J | A07 | \$D | *4 | D00881E | B12 | | | ALL | | |
| RK08 | 24 | FA | R2 | 0-0 | 27-41-11 | D05051J | A08 | \$D | *4 | D00881A | D11 | | | ALL | | |
| RK09 | 24 | FA | R2 | 0-0 | 27-61-12 | D05051J | A09 | \$D | *4 | D00881D | C11 | | | ALL | | |
| RK10 | 24 | FA | R2 | 0-0 | 27-21-12 | D05051J | A10 | \$D | *4 | D00881D | C13 | | | ALL | | |
| RK11 | 24 | FA | R2 | 0-0 | SPARE | D05051J | A11 | \$D | *4 | D00881A | REF | ** | | ALL | | |
| RK12 | 24 | FA | R2 | 0-0 | SPARE | D05051J | A12 | \$D | *4 | D00881A | REF | ** | | ALL | | |
| RK13 | 24 | FA | R2 | 0-0 | 27-09-14 | D05051J | A13 | \$D | *4 | D00881A | H14 | | | ALL | | |
| RK14 | 24 | FA | R2 | 0-0 | 27-09-14 | D05051J | A14 | \$D | *4 | D00881E | K13 | | | ALL | | |
| RK15 | 24 | FA | R2 | 0-0 | 27-09-14 | D05051J | A15 | \$D | *4 | D00881E | J11 | | | ALL | | |
| RK16 | 24 | FA | R2 | 0-0 | 27-09-14 | D05051J | A16 | \$D | *4 | D00881E | K09 | | | ALL | | |
| RK17 | 24 | FA | R2 | 0-0 | SPARE | D05051J | A17 | \$D | *4 | D00881A | REF | ** | | ALL | | |
| RK18 | 24 | FA | R2 | 0-0 | SPARE | D05051J | A18 | \$D | *4 | D00881A | REF | ** | | ALL | | |
| RK19 | 24 | FA | R2 | 0-0 | SPARE | D05051J | A19 | \$D | *4 | D00881A | REF | ** | | ALL | | |
| RK20 | 24 | FA | R2 | 0-0 | 99-99-99 | D05051J | A20 | \$D | *4 | D00881A | REF | | | 050-099, 150-154, 275-276 | | |
| RK20 | 24 | FA | R2 | 0-0 | SPARE | D05051J | A20 | \$D | *4 | D00881A | REF | | | 155-199, 277-299 | | |
| RM01 | 24 | FA | R1 | 0-0 | 99-99-99 | D05051J | A01 | \$D | *4 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| RM01 | 24 | FA | R1 | 0-0 | SPARE | D05051J | A01 | \$D | *4 | D00883A | REF | | | 155-199, 277-299 | | |
| RM02 | 24 | FA | R1 | 0-0 | 22-21-11 | D05051J | A02 | \$D | *4 | D00883D | A06 | | | ALL | | |
| RM03 | 24 | FA | R1 | 0-0 | SPARE | D05051J | A03 | \$D | *4 | D00883A | REF | ** | | ALL | | |
| RM04 | 24 | FA | R1 | 0-0 | 27-09-14 | D05051J | A04 | \$D | *4 | TB0237X | A007 | BJ | | ALL | | |
| RM05 | 24 | FA | R1 | 0-0 | 27-09-14 | D05051J | A05 | \$D | *4 | TB0237X | A008 | BJ | | ALL | | |
| RM06 | 24 | FA | R1 | 0-0 | 27-11-12 | D05051J | A06 | \$D | *4 | D00883D | C03 | | | ALL | | |
| RM07 | 24 | FA | R1 | 0-0 | 27-41-11 | D05051J | A07 | \$D | *4 | D00883E | B12 | | | ALL | | |
| RM08 | 24 | FA | R1 | 0-0 | 27-41-11 | D05051J | A08 | \$D | *4 | D00883A | D11 | | | ALL | | |
| RM09 | 24 | FA | R1 | 0-0 | 27-61-12 | D05051J | A09 | \$D | *4 | D00883D | C11 | | | ALL | | |
| RM10 | 24 | FA | R1 | 0-0 | 27-21-12 | D05051J | A10 | \$D | *4 | D00883D | C13 | | | ALL | | |
| RM11 | 24 | FA | R1 | 0-0 | SPARE | D05051J | A11 | \$D | *4 | D00883A | REF | ** | | ALL | | |
| RM12 | 24 | FA | R1 | 0-0 | SPARE | D05051J | A12 | \$D | *4 | D00883A | REF | ** | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 75

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|---------|------|------|---------------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2002 | 286T2002 | | | E8 SHELF-FLAT CABLE ASSY 2 (continued) | | | | | | | | | | | | |
| RM13 | 24 | FA | R1 | 0-0 | 27-09-14 | D05051J | A13 | \$D | *4 | TB0237X | C008 | BJ | | ALL | | |
| RM14 | 24 | FA | R1 | 0-0 | 27-09-14 | D05051J | A14 | \$D | *4 | D00883E | K13 | | | ALL | | |
| RM15 | 24 | FA | R1 | 0-0 | 27-09-14 | D05051J | A15 | \$D | *4 | D00883E | J11 | | | ALL | | |
| RM16 | 24 | FA | R1 | 0-0 | 27-09-14 | D05051J | A16 | \$D | *4 | TB0237X | D008 | BJ | | ALL | | |
| RM17 | 24 | FA | R1 | 0-0 | SPARE | D05051J | A17 | \$D | *4 | D00883A | REF | ** | | ALL | | |
| RM18 | 24 | FA | R1 | 0-0 | SPARE | D05051J | A18 | \$D | *4 | D00883A | REF | ** | | ALL | | |
| RM19 | 24 | FA | R1 | 0-0 | SPARE | D05051J | A19 | \$D | *4 | D00883A | REF | ** | | ALL | | |
| RM20 | 24 | FA | R1 | 0-0 | 99-99-99 | D05051J | A20 | \$D | *4 | D00883A | REF | | | 050-099, 150-154, 275-276 | | |
| RM20 | 24 | FA | R1 | 0-0 | SPARE | D05051J | A20 | \$D | *4 | D00883A | REF | | | 155-199, 277-299 | | |
| W2004 | 286T2004 | | | E8 SHELF-POWER, GROUNDS L | | | | | | | | | | | | |
| 001 | 22 | PA | | 4-0 | 31-41-11 | D06254J | | | 1 | D00881C | | 1 | | ALL | | |
| 004 | 20 | PA | | 3-0 | 31-41-11 | D00881C | | | 4 | GD00093 | A.. | 2 | | ALL | | |
| 005 | 20 | PA | | 3-0 | 31-41-11 | D00881C | | | 5 | GD00093 | D.. | 2 | | ALL | | |
| 006 | 20 | PA | | 3-0 | 31-41-11 | D00881C | | | 6 | GD00093 | S.. | 2 | | ALL | | |
| 008 | 24 | PK | | 3-0 | 24-25-13 | D00883F | | | J04 | TB0237Y | A001 | BJ | | ALL | | |
| 009 | 24 | PK | | 3-0 | 24-25-13 | D00881E | | | B13 | TB0237Y | C001 | BJ | | ALL | | |
| 016 | 24 | PK | | 4-0 | 24-25-13 | D06254J | | | 6 | D00883F | A03 | | | ALL | | |
| 017 | 24 | PK | | 4-0 | 24-25-13 | D06254J | | | 7 | D00883E | G08 | | | ALL | | |
| 018 | 24 | PK | | 3-0 | 24-25-13 | D06254J | | | 8 | TB0237Y | A001 | BJ | | ALL | | |
| 019 | 24 | PK | | 3-0 | 24-25-13 | D06254J | | | 9 | TB0237Y | C001 | BJ | | ALL | | |
| 021 | 22 | PA | | 3-0 | 31-41-11 | D00881A | | | K15 | GD00093 | D.. | 2 | | ALL | | |
| 022 | 22 | PA | | 3-0 | 31-41-11 | D00881B | | | K15 | GD00083 | D.. | 2 | | 050-099, 150-154, 162-164, 275-276 | | |
| 022 | 22 | PA | | 3-0 | 31-41-11 | D00881B | | | K15 | GDX0002 | D.. | 2 | | 155-157, 165-199, 277-299 | | |
| 023 | 22 | PA | | 3-0 | 31-41-11 | D00881D | | | K15 | GD00093 | D.. | 2 | | ALL | | |
| 024 | 22 | PA | | 3-0 | 31-41-11 | D00881E | | | K15 | GD00093 | D.. | 2 | | ALL | | |
| 025 | 22 | PA | | 4-0 | 31-41-32 | D00881F | | | G10 | TB0237Z | 9 | BJ | | ALL | | |
| 026 | 22 | PA | | 1-0 | 31-41-32 | TB0237Z | | | 10 | TB0237Z | 9 | BJ | | ALL | | |
| 029 | 22 | PA | | 4-0 | 31-41-34 | D00881E | | | E04 | TB0237Z | 17 | BJ | | ALL | | |
| 038 | 24 | PK | | 3-0 | 24-25-13 | D00881F | | | J04 | TB0237Y | A001 | BJ | | ALL | | |
| 039 | 24 | PK | | 3-0 | 24-25-13 | D00883E | | | B13 | TB0237Y | C001 | BJ | | ALL | | |
| 201B | 24 | PW | IA | 3-0 | 31-41-31 | D00881E | | | F12 | TB0237X | B003 | BJ | | 050-099, 150-199 | | |
| 201B | 24 | PW | IA | 3-0 | 31-41-31 | D00881E | | | F12 | TB0237Z | 4 | BJ | | 275-299 | | |
| 201R | 24 | PW | IA | 0-0 | 31-41-31 | D00881E | | | F11 | TB0237X | A003 | BJ | | 050-099, 150-199 | | |
| 201R | 24 | PW | IA | 0-0 | 31-41-31 | D00881E | | | F11 | TB0237Z | 3 | BJ | | 275-299 | | |
| 201Z | | | IA | 0-0 | 31-41-31 | TB0237X | | | | FA | GD00089 | S.. | 2 | 050-099 | | |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 76

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|---------------------------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2004 | 286T2004 | | | E8 SHELF-POWER, GROUNDS L (continued) | | | | | | | | | | | |
| 201Z | | | | IA | 0-0 | 31-41-31 | TB0237X | | | FA | GD00083 | S.. | 2 | 150-154, 162-164 | |
| 201Z | | | | IA | 0-0 | 31-41-31 | TB0237X | | | FA | GD00002 | S.. | 2 | 155-157, 165-199 | |
| 201Z | | | | IA | 0-0 | 31-41-31 | TB0237Z | | | FA | GD00083 | S.. | 2 | 275-276 | |
| 201Z | | | | IA | 0-0 | 31-41-31 | TB0237Z | | | FA | GD00002 | S.. | 2 | 277-299 | |
| 205B | 24 | PW | | IE | 3-0 | 31-41-32 | D00881B | | C13 | | TB0237X | B003 | BJ | 050-099, 150-199 | |
| 205B | 24 | PW | | IE | 3-0 | 31-41-32 | D00881B | | C13 | | TB0237Z | 4 | BJ | 275-299 | |
| 205R | 24 | PW | | IE | 0-0 | 31-41-32 | D00881B | | C12 | | TB0237X | A003 | BJ | 050-099, 150-199 | |
| 205R | 24 | PW | | IE | 0-0 | 31-41-32 | D00881B | | C12 | | TB0237Z | 3 | BJ | 275-299 | |
| 205Z | | | | IE | 0-0 | 31-41-32 | TB0237X | | | FA | GD00089 | S.. | 2 | 050-099 | |
| 205Z | | | | IE | 0-0 | 31-41-32 | TB0237X | | | FA | GD00083 | S.. | 2 | 150-154, 162-164 | |
| 205Z | | | | IE | 0-0 | 31-41-32 | TB0237X | | | FA | GD00002 | S.. | 2 | 155-157, 165-199 | |
| 205Z | | | | IE | 0-0 | 31-41-32 | TB0237Z | | | FA | GD00083 | S.. | 2 | 275-276 | |
| 205Z | | | | IE | 0-0 | 31-41-32 | TB0237Z | | | FA | GD00002 | S.. | 2 | 277-299 | |
| 207B | 24 | PW | | IG | 3-0 | 31-41-32 | D00881A | | F12 | | TB0237X | B013 | BJ | ALL | |
| 207R | 24 | PW | | IG | 0-0 | 31-41-32 | D00881A | | E12 | | TB0237X | A013 | BJ | ALL | |
| 207Z | | | | IG | 0-0 | 31-41-32 | GD00081 | | S.. | 2 | TB0237X | A014 | BJ | 050-099, 150-154, 162-164, 275-276 | |
| 207Z | | | | IG | 0-0 | 31-41-32 | GD00002 | | S.. | 2 | TB0237X | A014 | BJ | 155-157, 165-199, 277-299 | |
| 209B | 24 | PW | | II | 3-0 | 31-41-34 | D00881E | | F06 | | TB0237X | D013 | BJ | ALL | |
| 209R | 24 | PW | | II | 0-0 | 31-41-34 | D00881E | | F05 | | TB0237X | C013 | BJ | ALL | |
| 209Z | | | | II | 0-0 | 31-41-34 | GD00083 | | S.. | 2 | TB0237X | D014 | BJ | 050-099, 150-154, 162-164, 275-276 | |
| 209Z | | | | II | 0-0 | 31-41-34 | GD00002 | | S.. | 2 | TB0237X | D014 | BJ | 155-157, 165-199, 277-299 | |
| W2006 | 286T2006 | | | E8 SHELF-POWER, GROUNDS R | | | | | | | | | | | |
| 001 | 22 | PA | | | 4-0 | 31-41-11 | D06256J | | 1 | | D00883C | 1 | | ALL | |
| 004 | 20 | PA | | | 3-0 | 31-41-11 | D00883C | | 4 | | GD00171 | A.. | 2 | ALL | |
| 005 | 20 | PA | | | 3-0 | 31-41-11 | D00883C | | 5 | | GD00171 | D.. | 2 | ALL | |
| 006 | 20 | PA | | | 3-0 | 31-41-11 | D00883C | | 6 | | GD00171 | S.. | 2 | ALL | |
| 007 | 22 | PA | | | 3-0 | 31-41-17 | D06256J | | 7 | | TB0239Z | 34 | BJ | ALL | |
| 008 | 24 | PK | | | 6-0 | 31-41-13 | D06256J | | 8 | | S00612 | 1 | C | ALL | |
| 009 | 24 | PK | | | 6-0 | 31-41-13 | D06256J | | 9 | | S00612 | 2 | C | ALL | |
| 020 | 20 | PA | | | 7-0 | 31-41-13 | GD00083 | | D.. | 2 | S00612 | 3 | C | 050-099 | |
| 020 | 20 | PA | | | 7-0 | 31-41-13 | GD00089 | | D.. | 2 | S00612 | 3 | C | 150-154, 162-164, 275-276 | |
| 020 | 20 | PA | | | 7-0 | 31-41-13 | GD00001 | | D.. | 2 | S00612 | 3 | C | 155-157, 165-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 77
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2006 | 286T2006 | | | E8 SHELF-POWER, GROUNDS R (continued) | | | | | | | | | | | | |
| 021 | 22 | | PA | 4-0 | 31-41-11 | D00883A | | K15 | | | | | GD00171 | D.. | 2 | ALL |
| 022 | 22 | | PA | 3-0 | 31-41-11 | D00883B | | K15 | | | | | GD00169 | D.. | 2 | 050-099, 150-154, 162-164, 275-276 |
| 022 | 22 | | PA | 3-0 | 31-41-11 | D00883B | | K15 | | | | | GDX0001 | D.. | 2 | 155-157, 165-199, 277-299 |
| 023 | 22 | | PA | 3-0 | 31-41-11 | D00883D | | K15 | | | | | GD00171 | D.. | 2 | ALL |
| 024 | 22 | | PA | 3-0 | 31-41-11 | D00883E | | K15 | | | | | GD00171 | D.. | 2 | ALL |
| 025 | 22 | | PA | 3-0 | 31-41-32 | D00883F | | G10 | | | | | TB0237Z | 10 | BJ | ALL |
| 029 | 22 | | PA | 3-0 | 31-41-34 | D00883E | | E04 | | | | | TB0237Z | 18 | BJ | ALL |
| 030 | 22 | | PA | 2-0 | 31-41-34 | TB0237Z | | 17 | BJ | | | | TB0237Z | 18 | BJ | ALL |
| 031 | 22 | | PA | 3-0 | 49-71-11 | TB0237R | | C019 | 2 | | | | D00883F | A05 | | ALL |
| 032 | 20 | | PA | 3-0 | 49-71-11 | TB0237R | | A019 | 2 | | | | GD00169 | D.. | 2 | 050-099, 150-154, 162-164, 275-276 |
| 032 | 20 | | PA | 3-0 | 49-71-11 | TB0237R | | A019 | 2 | | | | GDX0001 | D.. | 2 | 155-157, 165-199, 277-299 |
| 033 | 22 | | PA | 3-0 | 49-73-11 | TB0237R | | C020 | 2 | | | | D00883F | A06 | | ALL |
| 034 | 20 | | PA | 3-0 | 49-73-11 | TB0237R | | A020 | 2 | | | | GD00169 | D.. | 2 | 050-099, 150-154, 162-164, 275-276 |
| 034 | 20 | | PA | 3-0 | 49-73-11 | TB0237R | | A020 | 2 | | | | GDX0001 | D.. | 2 | 155-157, 165-199, 277-299 |
| 035 | 24 | | PK | 4-0 | 27-18-11 | TB0239Y | | A041 | BJ | | | | GDX0001 | S.. | 2 | 155-157, 166-199, 277-299 |
| 036 | 24 | | PK | 4-0 | 27-18-11 | TB0239Y | | C041 | BJ | | | | D00881E | H05 | | 155-157, 166-199, 277-299 |
| 037 | 24 | | PK | 4-0 | 27-18-11 | TB0239Y | | A042 | BJ | | | | GDX0001 | S.. | 2 | 155-157, 166-199, 277-299 |
| 038 | 24 | | PK | 4-0 | 27-18-11 | TB0239Y | | C042 | BJ | | | | D00881E | H03 | | 155-157, 166-199, 277-299 |
| 039 | 24 | | PK | 4-0 | 27-18-11 | TB0239Y | | A043 | BJ | | | | D00881E | H02 | | 155-157, 166-199, 277-299 |
| 040 | 24 | | PK | 4-0 | 27-18-11 | TB0239Y | | A044 | BJ | | | | D00881E | H04 | | 155-157, 166-199, 277-299 |
| 041 | 24 | | PK | 4-0 | 27-18-11 | TB0239Y | | C041 | BJ | | | | D00883E | H05 | | 155-157, 166-199, 277-299 |
| 042 | 24 | | PK | 4-0 | 27-18-11 | TB0239Y | | C042 | BJ | | | | D00883E | H03 | | 155-157, 166-199, 277-299 |
| 043 | 24 | | PK | 4-0 | 27-18-11 | TB0239Y | | A043 | BJ | | | | D00883E | H02 | | 155-157, 166-199, 277-299 |

WIRE LIST

D280T132

91-21-11

Section W2000

Page 78

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|---------|-------|------|------|--------|------------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2006 | 286T2006 | | | E8 SHELF-POWER, GROUNDS R (continued) | | | | | | | | | | | | |
| 044 | 24 | | PK | 4-0 | 27-18-11 | TB0239Y | C043 | BJ | | GDX0001 | S.. | 2 | | | 155-157, 166-199, 277-299 | |
| 045 | 24 | | PK | 4-0 | 27-18-11 | TB0239Y | A044 | BJ | | D00883E | H04 | | | | 155-157, 166-199, 277-299 | |
| 046 | 24 | | PK | 4-0 | 27-18-11 | TB0239Y | C044 | BJ | | GDX0001 | S.. | 2 | | | 155-157, 166-199, 277-299 | |
| 201B | 24 | | PW | IA | 4-0 | 31-41-33 | D00883E | F12 | | TB0237X | D003 | BJ | | | 050-099 | |
| 201B | 24 | | PW | IA | 3-0 | 31-41-33 | D00883E | F12 | | TB0237X | D003 | BJ | | | 150-199 | |
| 201B | 24 | | PW | IA | 4-0 | 31-41-33 | D00883E | F12 | | TB0237Z | 6 | BJ | | | 275-299 | |
| 201R | 24 | | PW | IA | 0-0 | 31-41-33 | D00883E | F11 | | TB0237X | C003 | BJ | | | 050-099, 150-199 | |
| 201R | 24 | | PW | IA | 0-0 | 31-41-33 | D00883E | F11 | | TB0237Z | 5 | BJ | | | 275-299 | |
| 201Z | | | | IA | 0-0 | 31-41-33 | GD00151 | S.. | 2 | TB0237X | | | FA | | 050-099, 150-154, 162-164 | |
| 201Z | | | | IA | 0-0 | 31-41-33 | GDX0001 | S.. | 2 | TB0237X | | | FA | | 155-157, 165-199 | |
| 201Z | | | | IA | 0-0 | 31-41-33 | GD00151 | S.. | 2 | TB0237Z | | | FA | | 275-276 | |
| 201Z | | | | IA | 0-0 | 31-41-33 | GDX0001 | S.. | 2 | TB0237Z | | | FA | | 277-299 | |
| 205B | 24 | | PW | IE | 4-0 | 31-41-34 | D00883B | C13 | | TB0237X | D003 | BJ | | | 050-099 | |
| 205B | 24 | | PW | IE | 3-0 | 31-41-34 | D00883B | C13 | | TB0237X | D003 | BJ | | | 150-199 | |
| 205B | 24 | | PW | IE | 4-0 | 31-41-34 | D00883B | C13 | | TB0237Z | 6 | BJ | | | 275-299 | |
| 205R | 24 | | PW | IE | 0-0 | 31-41-34 | D00883B | C12 | | TB0237X | C003 | BJ | | | 050-099, 150-199 | |
| 205R | 24 | | PW | IE | 0-0 | 31-41-34 | D00883B | C12 | | TB0237Z | 5 | BJ | | | 275-299 | |
| 205Z | | | | IE | 0-0 | 31-41-34 | GD00151 | S.. | 2 | TB0237X | | | FA | | 050-099, 150-154, 162-164 | |
| 205Z | | | | IE | 0-0 | 31-41-34 | GDX0001 | S.. | 2 | TB0237X | | | FA | | 155-157, 165-199 | |
| 205Z | | | | IE | 0-0 | 31-41-34 | GD00151 | S.. | 2 | TB0237Z | | | FA | | 275-276 | |
| 205Z | | | | IE | 0-0 | 31-41-34 | GDX0001 | S.. | 2 | TB0237Z | | | FA | | 277-299 | |
| 207B | 24 | | PW | IG | 3-0 | 31-41-34 | D00883A | F12 | | TB0237X | D013 | BJ | | | ALL | |
| 207R | 24 | | PW | IG | 0-0 | 31-41-34 | D00883A | E12 | | TB0237X | C013 | BJ | | | ALL | |
| 207Z | | | | IG | 0-0 | 31-41-34 | GD00159 | S.. | 2 | TB0237X | D014 | BJ | | | 050-099, 150-154, 162-164, 275-276 | |
| 207Z | | | | IG | 0-0 | 31-41-34 | GDX0001 | S.. | 2 | TB0237X | D014 | BJ | | | 155-157, 165-199, 277-299 | |
| 209B | 24 | | PW | II | 3-0 | 31-41-32 | D00883E | F06 | | TB0237X | B013 | BJ | | | ALL | |
| 209R | 24 | | PW | II | 0-0 | 31-41-32 | D00883E | F05 | | TB0237X | A013 | BJ | | | ALL | |
| 209Z | | | | II | 0-0 | 31-41-32 | GD00151 | S.. | 2 | TB0237X | A014 | BJ | | | 050-099, 150-154, 162-164, 275-276 | |
| 209Z | | | | II | 0-0 | 31-41-32 | GDX0001 | S.. | 2 | TB0237X | A014 | BJ | | | 155-157, 165-199, 277-299 | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 79
Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2008 | 286T2008 | | | CREW REST CONTROL MODULE - FWD-JUMPER | | | | | | | | | | | |
| 001 | 24 | | PK | 2-0 | 33-21-31 | S00818 | = 1 | C | | D06900J | 5 | | | 050-099, 162-199 | |
| 002 | 24 | | PK | 2-0 | 33-21-31 | S00818 | = 2 | C | | D06900J | 6 | | | 050-099, 162-199 | |
| 003 | 20 | | PA | 2-0 | 26-13-12 | D12258 | 7 | | | D06900J | 2 | | | 050-099, 162-199 | |
| 004 | 20 | | PA | 2-0 | 26-13-12 | D12258 | 15 | | | D06900J | 3 | | | 050-099, 162-199 | |
| 005 | 20 | | PA | 2-0 | 26-13-12 | D12258 | 1 | | | D06900J | 4 | | | 050-099, 162-199 | |
| 006 | 20 | | PA | 2-0 | 26-13-12 | D12258 | 2 | | | D06900J | 1 | | | 050-099, 162-163 | |
| 006 | 20 | | PA | 2-0 | 26-13-12 | D12258 | 2 | | | SM00001 | | 9 | | 164-199 | |
| 008 | 20 | | PA | 2-0 | 26-13-12 | D12258 | 8 | | | D06900J | 8 | | | 050-099, 162-199 | |
| 009 | 22 | | PA | 2-0 | 21-66-21 | D12258 | 3 | | | D06900J | 9 | | | 050-099 | |
| 009 | 22 | | PA | 2-0 | 21-66-21 | D06900J | 9 | | | D12258 | 3 | | | 162-199 | |
| 010 | 22 | | PA | 2-0 | 21-66-21 | D12258 | 12 | | | D06900J | 11 | | | 050-099 | |
| 010 | 22 | | PA | 2-0 | 21-66-21 | D06900J | 11 | | | D12258 | 12 | | | 162-199 | |
| 011 | 20 | | PA | 1-0 | 26-13-12 | D06900J | 1 | | | SM00001 | | 9 | | 164-199 | |
| 012 | 20 | | PA | 1-0 | 26-13-12 | D06900J | 12 | | | SM00001 | | 9 | | 164-199 | |

WIRE LIST
D280T132

91-21-11
Section W2000
Page 80 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|----|-----------------|----|-----|-------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2010 | | 286T2010 | | | AFT CLOSET | | | | | | | | | | | |
| 001 | 22 | | PA | | 8-0 | 33-22-21 | D12086P | =1 | | | S00526 | =1 | C | * | 151-152 | |
| 002 | 22 | | PA | | 5-0 | 33-22-21 | S00526 | =2 | C | | L00411 | =P | C | | 151-152 | |
| 003 | 22 | | PA | | 8-0 | 33-22-21 | D12088J | =1 | | | L00411 | =G | C | * | 151-152 | |
| 004 | 22 | | PA | | 9-0 | 33-22-21 | L00411 | =G | C | * | L00607 | =G | C | | 151-152 | |
| 005 | 22 | | PA | | 5-0 | 33-22-21 | S00540 | =2 | C | | L00607 | =P | C | | 151-152 | |
| 006 | 22 | | PA | | 8-0 | 33-22-21 | S00540 | =1 | C | | S00526 | =1 | C | * | 151-152 | |
| 901 | 22 | | PA | | 10-0 | 33-22-21 | D12086P | =1 | | | SMZ0001 | | S | | 162-199 | |
| 902 | 22 | | PA | | 10-0 | 33-22-21 | D12088J | =1 | | | SMZ0002 | | S | | 162-199 | |
| 903 | 22 | | PA | | 10-0 | 33-22-21 | S09004 | =1 | C | | SMZ0001 | | S | | 162-199 | |
| 904 | 22 | | PA | | 10-0 | 33-22-21 | SMZ0002 | | S | | L09004 | =G | C | | 162-199 | |
| 905 | 22 | | PA | | 10-0 | 33-22-21 | S09004 | =2 | C | | L09004 | =P | C | | 162-199 | |
| 906 | 22 | | PA | | 10-0 | 33-22-21 | SMZ0001 | | S | | S09005 | =1 | C | | 162-199 | |
| 907 | 22 | | PA | | 10-0 | 33-22-21 | SMZ0002 | | S | | L09005 | =G | C | | 162-199 | |
| 908 | 22 | | PA | | 10-0 | 33-22-21 | S09005 | =2 | C | | L09005 | =P | C | | 162-199 | |
| 909 | 22 | | PA | | 10-0 | 33-22-21 | S09006 | =1 | C | | S09005 | =1 | C | | 162-199 | |
| 910 | 22 | | PA | | 10-0 | 33-22-21 | L09005 | =G | C | | L09006 | =G | C | | 162-199 | |
| 911 | 22 | | PA | | 10-0 | 33-22-21 | S09006 | =2 | C | | L09006 | =P | C | | 162-199 | |

WIRE LIST
D280T132

91-21-11
Section W2010
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W2024 | 286T2024 | | | CREW REST CONTROL MODULE - JUMPER PLUG. | | | | | | | | | | |
| 001 | 24 | | PK | 2-0 | 33-21-31 | D06902J | | 5 | | D06902J | | 7 | | 050-099, 162-199 |
| W2029 | 286T2029 | | | AFT DIVIDER-LAV OCC SIGN-SHORTING PLUG | | | | | | | | | | |
| 001 | 20 | | PA | 2-0 | 33-26-21 | D06237 | | 13 | | D06237 | | 14 | | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W2020
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2040 | 286T2040 | | | CREW REST CONTROL MODULE - AFT-JUMPER | | | | | | | | | | | |
| 001 | 24 | | PK | | 3-0 | 33-21-31 | S00828 | = 1 | C | | D06976J | | 5 | | 050-099, 150, 152-199 |
| 002 | 24 | | PK | | 3-0 | 33-21-31 | S00828 | = 2 | C | | D06976J | | 6 | | 050-099, 150, 152-199 |
| 003 | 20 | | PA | | 8-0 | 26-13-12 | D12354 | | 7 | | D06976J | | 2 | | 050-099, 162-199 |
| 003 | 20 | | PA | | 8-0 | 26-13-12 | D12354 | | 7 | | D13494 | | 2 | | 150, 152-157 |
| 004 | 20 | | PA | | 8-0 | 26-13-12 | D12354 | | 15 | | D06976J | | 3 | | 050-099, 162-199 |
| 004 | 20 | | PA | | 8-0 | 26-13-12 | D12354 | | 15 | | D13494 | | 3 | | 150, 152-157 |
| 005 | 20 | | PA | | 8-0 | 26-13-12 | D12354 | | 1 | | D06976J | | 4 | | 050-099, 162-199 |
| 005 | 20 | | PA | | 8-0 | 26-13-12 | D12354 | | 1 | | D13494 | | 4 | | 150, 152-157 |
| 006 | 20 | | PA | | 8-0 | 26-13-12 | D12354 | | 2 | | D06976J | | 1 | | 050-099, 162-163 |
| 006 | 20 | | PA | | 8-0 | 26-13-12 | D12354 | | 2 | | D13494 | | 1 | | 150, 152-157 |
| 006 | 20 | | PA | | 8-0 | 26-13-12 | D12354 | | 2 | | SM00001 | | | 9 | 164-199 |
| 008 | 20 | | PA | | 8-0 | 26-13-12 | D12354 | | 8 | | D06976J | | 8 | | 050-099, 162-199 |
| 008 | 20 | | PA | | 8-0 | 26-13-12 | D12354 | | 8 | | D13494 | | 8 | | 150, 152-157 |
| 009 | 22 | | PA | | 8-0 | 21-66-31 | D12354 | | 3 | | D06976J | | 9 | | 050-099, 162-199 |
| 009 | 22 | | PA | | 8-0 | 21-66-31 | D12354 | | 3 | | D13494 | | 9 | | 150, 152-157 |
| 010 | 22 | | PA | | 8-0 | 21-66-31 | D12354 | | 12 | | D06976J | | 11 | | 050-099, 162-199 |
| 010 | 22 | | PA | | 8-0 | 21-66-31 | D12354 | | 12 | | D13494 | | 11 | | 150, 152-157 |
| 011 | 20 | | PA | | 1-0 | SPARE | D06976J | | 1 | | SM00001 | | | 9 | 150, 152-157 |
| 011 | 20 | | PA | | 1-0 | 26-13-12 | D06976J | | 1 | | SM00001 | | | 9 | 164-199 |
| 012 | 20 | | PA | | 1-0 | SPARE | D06976J | | 12 | | SM00001 | | | 9 | 150, 152-157 |
| 012 | 20 | | PA | | 1-0 | 26-13-12 | D06976J | | 12 | | SM00001 | | | 9 | 164-199 |

WIRE LIST
D280T132

91-21-11
Section W2040
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|--------------|-----------------|----|-------|------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2052 | 286T2052 | | | SHELF E3-2 | | | | | | | | | | | | |
| 001 | 24 | | PK | | 3-0 | 21-51-23 | D10152B | | B12 | | | D06264P | | 1 | | ALL |
| 002 | 24 | | PK | | 3-0 | 21-51-23 | D10152B | | A12 | | | D06264P | | 2 | | ALL |
| 003 | 24 | | PK | | 3-0 | 21-51-23 | D10152B | | A15 | | | D06264P | | 3 | | ALL |
| 004 | 22 | | PA | | 3-0 | 21-51-23 | D10152B | | C15 | | | D06264P | | 8 | | ALL |
| 005 | 24 | | PK | | 3-0 | 21-51-13 | D10152A | | B12 | | | D06262P | | 1 | | ALL |
| 006 | 24 | | PK | | 3-0 | 21-51-13 | D10152A | | A12 | | | D06262P | | 2 | | ALL |
| 007 | 24 | | PK | | 3-0 | 21-51-13 | D10152A | | A15 | | | D06262P | | 3 | | ALL |
| 008 | 22 | | PA | | 3-0 | 21-51-13 | D10152A | | C15 | | | D06262P | | 8 | | ALL |
| 009 | 20 | | PA | | 3-0 | 21-51-13 | D10152C | | 3 | | | D06262P | | 9 | | ALL |
| 201B | 22 | | PB | A | 3-0 | 21-51-23 | D10152B | | A09 | | | D06264P | | 4 | | ALL |
| 201R | 22 | | PB | A | 0-0 | 21-51-23 | D10152B | | B09 | | | D06264P | | 5 | | ALL |
| 202B | 22 | | PB | B | 3-0 | 21-51-23 | D10152B | | A10 | | | D06264P | | 6 | | ALL |
| 202R | 22 | | PB | B | 0-0 | 21-51-23 | D10152B | | B10 | | | D06264P | | 7 | | ALL |
| 203B | 22 | | PB | C | 3-0 | 21-51-13 | D10152A | | A09 | | | D06262P | | 4 | | ALL |
| 203R | 22 | | PB | C | 0-0 | 21-51-13 | D10152A | | B09 | | | D06262P | | 5 | | ALL |
| 204B | 22 | | PB | D | 3-0 | 21-51-13 | D10152A | | A10 | | | D06262P | | 6 | | ALL |
| 204R | 22 | | PB | D | 0-0 | 21-51-13 | D10152A | | B10 | | | D06262P | | 7 | | ALL |
| W2058 | 286T2058 | | | HYD GEN SYS-H2-P65 INTERNAL | | | | | | | | | | | | |
| 001 | 22 | | PA | | 5-0 | 24-25-11 | TB0310Z | | 1 | BJ | | D06452J | | 6 | | ALL |
| 002 | 22 | | PA | | 1-0 | 24-25-11 | TB0310Z | | 1 | BJ | | D10790 | | B2 | | ALL |
| 003 | 22 | | PA | | 3-0 | 24-25-11 | TB0310Z | | 1 | BJ | | D10788 | | B1 | | ALL |
| 004 | 22 | | PA | | 5-0 | 24-25-11 | D10788 | | X1 | | | D06452J | | 1 | | ALL |
| 005 | 22 | | PA | | 3-0 | 24-25-11 | TB0310Y | | A010 | BJ | | D10788 | | A3 | | ALL |
| 006 | 20 | | PA | | 3-0 | 24-25-11 | D10788 | | X2 | | | GDX0001 | | A.. | 2 | ALL |
| 007 | 22 | | PA | | 5-0 | 24-25-11 | TB0310Y | | A010 | BJ | | D06452J | | 4 | | ALL |
| 008 | 22 | | PA | | 5-0 | 24-25-11 | TB0310Y | | A010 | BJ | | D06452J | | 7 | | ALL |
| 009 | 22 | | PA | | 1-0 | 24-25-11 | D10788 | | B2 | | | D10786 | | B2 | | ALL |
| 010 | 22 | | PA | | 1-0 | 24-25-11 | D10788 | | A2 | | | D10786 | | A2 | | ALL |
| 011 | 22 | | PA | | 5-0 | 24-25-11 | D10786 | | X1 | | | D06452J | | 2 | | ALL |
| 012 | 22 | | PA | | 3-0 | 24-25-11 | D10786 | | B1 | | | M01228 | | A | C | ALL |
| 013 | 22 | | PA | | 3-0 | 24-25-11 | D10786 | | A3 | | | M01230 | | A | C | ALL |
| 014 | 22 | | PA | | 3-0 | 24-25-11 | D10790 | | X2 | | | GDX0001 | | D.. | 2 | ALL |
| 015 | 22 | | PA | | 5-0 | 24-25-12 | SM00001 | | | W | | K00862 | | X1 | C | * ALL |
| 016 | 20 | | PA | | 5-0 | 24-25-12 | K00861 | | X2 | C | | GDX0002 | | D.. | 2 | ALL |
| 017 | 22 | | PA | | 3-0 | 24-25-11 | D10790 | | Y2 | | | GDX0001 | | D.. | 2 | ALL |
| 018 | 22 | | PA | | 3-0 | 24-25-11 | D10790 | | Y1 | | | M01228 | | B | C | ALL |
| 019 | 22 | | PA | | 3-0 | 24-25-12 | D10790 | | A2 | | | SM00001 | | W | | ALL |
| 020 | 22 | | PA | | 3-0 | 24-25-11 | D10790 | | X1 | | | M01230 | | B | C | ALL |

WIRE LIST

D280T132

91-21-11

Section W2050

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2058 | 286T2058 | | | HYD GEN SYS-H2-P65 INTERNAL (continued) | | | | | | | | | | | |
| 022 | 22 | | PA | | 3-0 | 24-25-11 | D10790 | | B1 | | TB0310Y | A004 | BJ | | ALL |
| 023 | 22 | | PA | | 3-0 | 24-25-12 | D10790 | | A1 | | D10836 | 14 | | | ALL |
| 030 | 22 | | PA | | 1-0 | 24-25-11 | TB0310Y | | A004 | BJ | TB0310Y | A006 | BJ | | ALL |
| 040 | 20 | | PA | | 5-0 | 24-25-11 | K00861 | | 12 | C | GDX0001 | D.. | 2 | | ALL |
| 042 | 22 | | PA | | 4-0 | 24-25-11 | TB0310Y | | A004 | BJ | D10832 | 7 | | | ALL |
| 046 | 22 | | PA | | 3-0 | 24-25-11 | D10832 | | 2 | | D10836 | 9 | | | ALL |
| 047 | 22 | | PA | | 3-0 | 24-25-11 | D10832 | | 4 | | D10836 | 10 | | | ALL |
| 048 | 22 | | PA | | 3-0 | 24-25-11 | D10792 | | X1 | | TB0310Y | A006 | BJ | | ALL |
| 049 | 20 | | PA | | 3-0 | 24-25-11 | D10792 | | X2 | | GDX0001 | D.. | 2 | | ALL |
| 050 | 22 | | PA | | 4-0 | 24-25-11 | TB0310Y | | A006 | BJ | D06460J | 1 | | | ALL |
| 051 | 22 | | PA | | 4-0 | 24-25-11 | D06460J | | 2 | | D10790 | B3 | | | ALL |
| 053 | 22 | | PA | | 4-0 | 24-25-11 | K00862 | | 12 | C | TB0310Z | 1 | BJ | | ALL |
| 054 | 22 | | PA | | 4-0 | 24-25-11 | K00861 | | 13 | C | D10832 | 3 | | | ALL |
| 055 | 22 | | PA | | 2-0 | 24-25-12 | K00862 | | X1 | C | K00863 | X1 | C | * | ALL |
| 056 | 20 | | PA | | 4-0 | 24-25-12 | K00862 | | X2 | C | GDX0001 | D.. | 2 | | ALL |
| 057 | 20 | | PA | | 4-0 | 24-25-12 | K00863 | | X2 | C | GDX0001 | D.. | 2 | | ALL |
| 058 | 22 | | PA | | 2-0 | 24-25-12 | K00863 | | X1 | C | K00864 | X1 | C | * | ALL |
| 059 | 20 | | PA | | 4-0 | 24-25-12 | K00864 | | X2 | C | GDX0001 | D.. | 2 | | ALL |
| 060 | 22 | | PA | | 4-0 | 24-25-12 | K00864 | | X1 | C | K00861 | X1 | C | * | ALL |
| 061 | 22 | | PA | | 5-0 | 24-25-11 | D06452J | | 3 | | TB0310Z | 1 | BJ | | ALL |
| 062 | 20 | | PA | | 3-0 | 24-25-12 | D10836 | | 6 | | TB5154 | 1 | E | | ALL |
| 063 | 20 | | PA | | 3-0 | 24-25-12 | D10836 | | 7 | | TB5154 | 2 | E | | ALL |
| 064 | 20 | | PA | | 3-0 | 24-25-12 | D10836 | | 8 | | TB5154 | 3 | E | | ALL |
| 065 | 20 | | PA | | 3-0 | 24-25-12 | D10836 | | 17 | | GDX0001 | A.. | 2 | | ALL |
| 066 | 20 | | PA | | 3-0 | 24-25-12 | D10836 | | 13 | | GDX0001 | D.. | 2 | | ALL |
| 067 | 12 | | PA | | 3-0 | 24-25-12 | K00862 | | C1 | E | K00863 | C1 | E | * | ALL |
| 068 | 12 | | PA | | 3-0 | 24-25-12 | K00862 | | B1 | E | K00863 | B1 | E | * | ALL |
| 069 | 12 | | PA | | 3-0 | 24-25-12 | K00862 | | A1 | E | K00863 | A1 | E | * | ALL |
| 070 | 12 | | PA | | 2-0 | 24-25-12 | K00864 | | C1 | E | K00863 | C1 | E | * | ALL |
| 071 | 12 | | PA | | 2-0 | 24-25-12 | K00864 | | B1 | E | K00863 | B1 | E | * | ALL |
| 072 | 12 | | PA | | 2-0 | 24-25-12 | K00864 | | A1 | E | K00863 | A1 | E | * | ALL |
| 073 | 12 | | PA | | 3-0 | 24-25-12 | D06462J | | 1 | | TB5154 | 1 | E | * | ALL |
| 074 | 12 | | PA | | 3-0 | 24-25-12 | D06462J | | 2 | | TB5154 | 2 | E | * | ALL |
| 075 | 12 | | PA | | 3-0 | 24-25-12 | D06462J | | 3 | | TB5154 | 3 | E | * | ALL |
| 076 | 12 | | PA | | 2-0 | 24-25-12 | K00862 | | C1 | E | TB5154 | 3 | E | * | ALL |
| 077 | 12 | | PA | | 2-0 | 24-25-12 | K00862 | | B1 | E | TB5154 | 2 | E | * | ALL |
| 078 | 12 | | PA | | 2-0 | 24-25-12 | K00862 | | A1 | E | TB5154 | 1 | E | * | ALL |
| 080 | 24 | | PK | | 2-0 | 24-25-13 | D06452J | | 8 | | C00845 | 2 | D | | ALL |
| 081 | 24 | | PK | | 2-0 | 24-25-13 | D06452J | | 9 | | C00846 | 2 | D | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W2050
 Page 2
 Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|----|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2058 | 286T2058 | | | HYD GEN SYS-H2-P65 INTERNAL (continued) | | | | | | | | | | | | | |
| 082 | 24 | | PK | 3-0 | 24-25-13 | D06452J | | 10 | | | | | K00862 | 11 | C | | ALL |
| 083 | 24 | | PK | 2-0 | 24-25-13 | D06452J | | 11 | | | | | D06460J | 12 | | | ALL |
| 084 | 06 | | PA | 1-6 | 24-25-13 | C00845 | | 1 | D | | | | K00861 | A1 | F7 | | ALL |
| 085 | 12 | | PA | 2-0 | 24-25-13 | C00846 | | 1 | D | | | | K00864 | B1 | E | * | ALL |
| 086 | 20 | | PA | 3-0 | 24-25-11 | D10786 | | X2 | | | | | GDX0001 | A.. | 2 | | ALL |
| 087 | 20 | | PA | 4-0 | 33-51-11 | K00864 | | 12 | C | | | | GDX0002 | A.. | 2 | | ALL |
| 088 | 22 | | PA | 5-0 | 29-11-32 | D06452J | | 13 | | | | | D10792 | A1 | | | ALL |
| 089 | 20 | | PA | 3-0 | 29-11-32 | D10792 | | A2 | | | | | GDX0002 | D.. | 2 | | ALL |
| 090 | 12 | | PA | 4-0 | 24-51-14 | D06454J | | 1 | | | | | K00863 | A2 | E | | ALL |
| 091 | 12 | | PA | 4-0 | 24-51-14 | D06454J | | 2 | | | | | K00863 | B2 | E | | ALL |
| 092 | 12 | | PA | 4-0 | 24-51-14 | D06454J | | 3 | | | | | K00863 | C2 | E | | ALL |
| 093 | 14 | | PA | 4-0 | 24-51-14 | D06456J | | 18 | | | | | K00863 | C3 | E | | ALL |
| 094 | 14 | | PA | 4-0 | 24-51-14 | D06456J | | 16 | | | | | K00863 | B3 | E | | ALL |
| 095 | 14 | | PA | 4-0 | 24-51-14 | D06456J | | 14 | | | | | K00863 | A3 | E | | ALL |
| 096 | 12 | | PA | 3-0 | 24-51-24 | D06458J | | 1 | | | | | K00864 | A2 | E | | ALL |
| 097 | 12 | | PA | 3-0 | 24-51-24 | D06458J | | 2 | | | | | K00864 | B2 | E | | ALL |
| 098 | 12 | | PA | 3-0 | 24-51-24 | D06458J | | 3 | | | | | K00864 | C2 | E | | ALL |
| 099 | 18 | | PA | 2-0 | 24-51-24 | D06474J | | 3 | | | | | K00864 | C3 | E | | ALL |
| 100 | 18 | | PA | 2-0 | 24-51-24 | D06474J | | 2 | | | | | K00864 | B3 | E | | ALL |
| 101 | 18 | | PA | 2-0 | 24-51-24 | D06474J | | 1 | | | | | K00864 | A3 | E | | ALL |
| 102 | 12 | | PA | 4-0 | 24-51-42 | D06454J | | 4 | | | | | K00862 | C2 | E | | ALL |
| 103 | 12 | | PA | 4-0 | 24-51-42 | D06454J | | 5 | | | | | K00862 | A2 | E | | ALL |
| 104 | 12 | | PA | 4-0 | 24-51-42 | D06454J | | 6 | | | | | K00862 | B2 | E | | ALL |
| 105 | 16 | | PA | 4-0 | 24-51-42 | D06456J | | 20 | | | | | K00862 | C3 | E | | ALL |
| 106 | 16 | | PA | 4-0 | 24-51-42 | D06456J | | 24 | | | | | K00862 | B3 | E | | ALL |
| 107 | 16 | | PA | 4-0 | 24-51-42 | D06456J | | 22 | | | | | K00862 | A3 | E | | ALL |
| 108 | 22 | | PA | 4-0 | 33-51-11 | D06452J | | 12 | | | | | K00864 | 11 | C | | ALL |
| 111 | 20 | | PA | 3-0 | 24-25-12 | D10836 | | 20 | | | | | GDX0002 | D.. | 2 | | ALL |
| 112 | 22 | | PA | 4-0 | 34-22-81 | D06456J | | 7 | | | | | K00863 | 12 | C | | ALL |
| 113 | 20 | | PA | 4-0 | 34-22-81 | K00863 | | 11 | C | | | | GDX0002 | D.. | 2 | | ALL |
| 114 | 22 | | PA | 5-0 | 24-25-12 | SM00001 | | | W | | | | K00861 | X1 | C | * | ALL |
| 201 | 20 | | UA | 1-6 | 24-25-12 | GDX0003 | | S.. | E | | | | D10836 | | | FA | ALL |
| 201B | 20 | | PR | IA | 3-0 | 24-25-12 | D10836 | 4 | | | | | D06460J | 10 | | | ALL |
| 201R | 20 | | PR | IA | 0-0 | 24-25-12 | D10836 | 5 | | | | | D06460J | 11 | | | ALL |
| 201Z | | | | IA | 0-0 | 24-25-12 | D10836 | | | | FA | | D06460J | 9 | | | ALL |
| 301B | 20 | | PC | MA | 3-0 | 24-25-12 | D10836 | 15 | | | | | D06460J | 3 | | | ALL |
| 301R | 20 | | PC | MA | 0-0 | 24-25-12 | D10836 | 16 | | | | | D06460J | 4 | | | ALL |
| 301Y | 20 | | PC | MA | 0-0 | 24-25-12 | D10836 | 11 | | | | | D06460J | 5 | | | ALL |
| 302B | 20 | | PC | MB | 3-0 | 24-25-12 | D10836 | 2 | | | | | D06460J | 6 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W2050

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|--|-------|----------|-------------|------|------|-----------|---------|--------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2058 | 286T2058 | | | HYD GEN SYS-H2-P65 INTERNAL (continued) | | | | | | | | | | | |
| 302R | 20 | PC | MB | | 0-0 | 24-25-12 | D10836 | | | 1 | D06460J | | 7 | | ALL |
| 302Y | 20 | PC | MB | | 0-0 | 24-25-12 | D10836 | | | 3 | D06460J | | 8 | | ALL |
| FRA | | | | | 0-0 | 24-25-12 | D10836 | | | | FA | D10836 | | 12 | ALL |

WIRE LIST
D280T132

91-21-11
Section W2050
Page 4 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----------------------|-------------|---------|-------|------|------|---------|-------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2062 | 286T2062 | | | CENTER PSU MOD | | | | | | | | | | | | |
| 001 | 18 | | PA | 3-0 | 33-24-13 | D05974J | 1 | DL | | SM00003 | | | S | | 275 | |
| 001 | 18 | | PA | 3-0 | 33-24-13 | D05974J | 1 | DL | | SM00001 | | | S | | 276-299 | |
| 002 | 18 | | PA | 2-0 | 33-24-13 | D05974J | 2 | DL | | SM00004 | | | S | | 275 | |
| 002 | 18 | | PA | 3-0 | 33-24-13 | D05974J | 2 | DL | | SM00002 | | | S | | 276-299 | |
| 003 | 20 | | PA | 3-0 | 33-24-13 | D08174 | 3 | | | SM00003 | | | S | | 275 | |
| 003 | 18 | | PA | 7-0 | 33-24-13 | SM00001 | | S | | SM00003 | | | S | | 276-299 | |
| 004 | 20 | | PA | 2-0 | 33-24-13 | D08174 | 4 | | | SM00004 | | | S | | 275 | |
| 004 | 18 | | PA | 7-0 | 33-24-13 | SM00002 | | S | | SM00004 | | | S | | 276-299 | |
| 005 | 20 | | PA | 8-0 | 33-24-13 | D08174 | 5 | | | GD00960 | A.. | 2 | | | 275 | |
| 005 | 18 | | PA | 6-0 | 33-24-13 | SM00003 | | S | | SM00005 | | | S | | 276-299 | |
| 006 | 18 | | PA | 6-0 | 33-24-13 | SM00004 | | S | | SM00006 | | | S | | 276-299 | |
| 007 | 18 | | PA | 4-0 | 33-24-13 | SM00005 | | S | | D08184P | | 1 | DK | | 276-299 | |
| 008 | 20 | | PA | 3-0 | 33-24-13 | SM00003 | | S | | D08176 | | 3 | | | 275 | |
| 008 | 18 | | PA | 4-0 | 33-24-13 | SM00006 | | S | | D08184P | | 2 | DK | | 276-299 | |
| 009 | 20 | | PA | 3-0 | 33-24-13 | SM00004 | | S | | D08176 | | 4 | | | 275 | |
| 010 | 20 | | PA | 6-0 | 33-24-13 | GD00960 | A.. | 2 | | D08176 | | 5 | | | 275 | |
| 013 | 20 | | PA | 2-0 | 33-24-13 | D08178 | 3 | | | SM00007 | | | S | | 275 | |
| 014 | 20 | | PA | 2-0 | 33-24-13 | D08178 | 4 | | | SM00008 | | | S | | 275 | |
| 015 | 20 | | PA | 7-0 | 33-24-13 | D08178 | 5 | | | GD04444 | A.. | 2 | | | 275 | |
| 016 | 18 | | PA | 6-0 | 33-24-13 | SM00003 | | S | | SM00007 | | | S | | 275 | |
| 017 | 18 | | PA | 7-0 | 33-24-13 | SM00004 | | S | | SM00008 | | | S | | 275 | |
| 018 | 20 | | PA | 3-0 | 33-24-13 | D08180 | 3 | | | SM00007 | | | S | | 275 | |
| 019 | 20 | | PA | 3-0 | 33-24-13 | D08180 | 4 | | | SM00008 | | | S | | 275 | |
| 020 | 20 | | PA | 4-0 | 33-24-13 | D08180 | 5 | | | GD04444 | A.. | 2 | | | 275 | |
| 021 | 18 | | PA | 7-0 | 33-24-13 | SM00007 | | S | | SM00009 | | | S | | 275 | |
| 022 | 18 | | PA | 7-0 | 33-24-13 | SM00008 | | S | | SM00010 | | | S | | 275 | |
| 023 | 20 | | PA | 2-0 | 33-24-13 | D08182 | 3 | | | SM00009 | | | S | | 275 | |
| 024 | 20 | | PA | 3-0 | 33-24-13 | D08182 | 4 | | | SM00010 | | | S | | 275 | |
| 025 | 20 | | PA | 6-0 | 33-24-13 | D08182 | 5 | | | GD01940 | A.. | 2 | | | 275 | |
| 026 | 18 | | PA | 4-0 | 33-24-13 | D08184P | 1 | DK | | SM00009 | | | S | | 275 | |
| 027 | 18 | | PA | 3-0 | 33-24-13 | D08184P | 2 | DK | | SM00010 | | | S | | 275 | |
| 103 | 20 | | PA | 3-0 | 33-24-13 | D08174 | 3 | | | SM00002 | | | S | | 276-299 | |
| 104 | 20 | | PA | 3-0 | 33-24-13 | D08174 | 4 | | | SM00001 | | | S | | 276-299 | |
| 105 | 20 | | PA | 8-0 | 33-24-13 | D08174 | 5 | | | GD00960 | A.. | 2 | | | 276-299 | |
| 113 | 20 | | PA | 4-0 | 33-24-13 | D08176 | 3 | | | SM00002 | | | S | | 276-299 | |
| 114 | 20 | | PA | 4-0 | 33-24-13 | D08176 | 4 | | | SM00001 | | | S | | 276-299 | |
| 115 | 20 | | PA | 6-0 | 33-24-13 | D08176 | 5 | | | GD00960 | A.. | 2 | | | 276-299 | |
| 123 | 20 | | PA | 3-0 | 33-24-13 | D08178 | 3 | | | SM00004 | | | S | | 276-299 | |
| 124 | 20 | | PA | 3-0 | 33-24-13 | D08178 | 4 | | | SM00003 | | | S | | 276-299 | |

WIRE LIST

D280T132

91-21-11

Section W2060

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2062 | 286T2062 | | | CENTER PSU MOD (continued) | | | | | | | | | | | |
| 125 | 20 | | PA | | 5-0 | 33-24-13 | D08178 | | | | GD00960 | A.. | 2 | | 276-299 |
| 133 | 20 | | PA | | 4-0 | 33-24-13 | D08180 | | | | SM00004 | | S | | 276-299 |
| 134 | 20 | | PA | | 4-0 | 33-24-13 | D08180 | | | | SM00003 | | S | | 276-299 |
| 135 | 20 | | PA | | 5-0 | 33-24-13 | D08180 | | | | GD04444 | A.. | 2 | | 276-299 |
| 143 | 20 | | PA | | 3-0 | 33-24-13 | D08182 | | | | SM00006 | | S | | 276-299 |
| 144 | 20 | | PA | | 3-0 | 33-24-13 | D08182 | | | | SM00005 | | S | | 276-299 |
| 145 | 20 | | PA | | 5-0 | 33-24-13 | D08182 | | | | GD01940 | A.. | 2 | | 276-299 |
| 201B | 22 | | PB | A | 3-0 | 23-31-16 | D05974J | | | | SM00014 | | S | | 275 |
| 201B | 22 | | PB | IA | 3-0 | 23-31-16 | D05974J | | | | SM00102 | | S | | 276-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-16 | D05974J | | | | SM00013 | | S | | 275 |
| 201R | 22 | | PB | IA | 0-0 | 23-31-16 | D05974J | | | | SM00101 | | S | | 276-299 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-16 | D08174 | | | | SM00102 | | S | | 276-299 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-16 | D08174 | | | | SM00101 | | S | | 276-299 |
| 203B | 22 | | PB | B | 3-0 | 23-31-16 | D08174 | | | | SM00014 | | S | | 275 |
| 203B | 22 | | PB | IC | 7-0 | 23-31-16 | SM00102 | | S | | SM00104 | | S | | 276-299 |
| 203R | 22 | | PB | B | 0-0 | 23-31-16 | D08174 | | 1 | | SM00013 | | S | | 275 |
| 203R | 22 | | PB | IC | 0-0 | 23-31-16 | SM00101 | | | S | SM00103 | | S | | 276-299 |
| 204B | 22 | | PB | E | 7-0 | 23-31-16 | SM00014 | | | S | SM00018 | | S | | 275 |
| 204B | 22 | | PB | ID | 4-0 | 23-31-16 | D08176 | | 2 | | SM00102 | | S | | 276-299 |
| 204R | 22 | | PB | E | 0-0 | 23-31-16 | SM00013 | | | S | SM00017 | | S | | 275 |
| 204R | 22 | | PB | ID | 0-0 | 23-31-16 | D08176 | | 1 | | SM00101 | | S | | 276-299 |
| 205B | 22 | | PB | D | 3-0 | 23-31-16 | D08176 | | 2 | | SM00014 | | S | | 275 |
| 205B | 22 | | PB | IE | 6-0 | 23-31-16 | SM00104 | | | S | SM00106 | | S | | 276-299 |
| 205R | 22 | | PB | D | 0-0 | 23-31-16 | D08176 | | 1 | | SM00013 | | S | | 275 |
| 205R | 22 | | PB | IE | 0-0 | 23-31-16 | SM00103 | | | S | SM00105 | | S | | 276-299 |
| 206B | 22 | | PB | IF | 3-0 | 23-31-16 | D08178 | | 2 | | SM00104 | | S | | 276-299 |
| 206R | 22 | | PB | IF | 0-0 | 23-31-16 | D08178 | | 1 | | SM00103 | | S | | 276-299 |
| 207B | 22 | | PB | F | 3-0 | 23-31-16 | D08178 | | 2 | | SM00018 | | S | | 275 |
| 207B | 22 | | PB | IG | 4-0 | 23-31-16 | SM00106 | | | S | D08184P | | 3 | | 276-299 |
| 207R | 22 | | PB | F | 0-0 | 23-31-16 | D08178 | | 1 | | SM00017 | | S | | 275 |
| 207R | 22 | | PB | IG | 0-0 | 23-31-16 | SM00105 | | | S | D08184P | | 4 | | 276-299 |
| 208B | 22 | | PB | H | 6-0 | 23-31-16 | SM00018 | | | S | SM00020 | | S | | 275 |
| 208B | 22 | | PB | IH | 4-0 | 23-31-16 | D08180 | | 2 | | SM00104 | | S | | 276-299 |
| 208R | 22 | | PB | H | 0-0 | 23-31-16 | SM00017 | | | S | SM00019 | | S | | 275 |
| 208R | 22 | | PB | IH | 0-0 | 23-31-16 | D08180 | | 1 | | SM00103 | | S | | 276-299 |
| 209B | 22 | | PB | I | 3-0 | 23-31-16 | D08180 | | 2 | | SM00018 | | S | | 275 |
| 209R | 22 | | PB | I | 0-0 | 23-31-16 | D08180 | | 1 | | SM00017 | | S | | 275 |
| 210B | 22 | | PB | J | 4-0 | 23-31-16 | SM00020 | | | S | D08184P | | 3 | | 275 |
| 210B | 22 | | PB | IJ | 3-0 | 23-31-16 | D08182 | | 2 | | SM00106 | | S | | 276-299 |

WIRE LIST
D280T132

91-21-11
Section W2060
Page 2
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2062 | 286T2062 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | |
| 210R | 22 | PB | J | 0-0 | 23-31-16 | SM00019 | | S | | D08184P | 4 | | | 275 | | |
| 210R | 22 | PB | IJ | 0-0 | 23-31-16 | D08182 | 1 | | | SM00105 | | S | | 276-299 | | |
| 211B | 22 | PB | K | 3-0 | 23-31-16 | SM00020 | | S | | D08182 | 2 | | | 275 | | |
| 211R | 22 | PB | K | 0-0 | 23-31-16 | SM00019 | | S | | D08182 | 1 | | | 275 | | |
| W2064 | 286T2064 | | | CENTER PSU MOD | | | | | | | | | | | | |
| 001 | 18 | PA | | 3-0 | 33-24-13 | D08186J | 1 | DL | | SM00001 | | S | | 150-199, 275-299 | | |
| 002 | 18 | PA | | 3-0 | 33-24-13 | D08186J | 2 | DL | | SM00002 | | S | | 150-199, 275-299 | | |
| 003 | 20 | PA | | 3-0 | 33-24-13 | D08188 | 3 | | | SM00001 | | S | | 150-199, 275 | | |
| 003 | 18 | PA | | 7-0 | 33-24-13 | SM00001 | | S | | SM00003 | | S | | 276-299 | | |
| 004 | 20 | PA | | 3-0 | 33-24-13 | D08188 | 4 | | | SM00002 | | S | | 150-199, 275 | | |
| 004 | 18 | PA | | 7-0 | 33-24-13 | SM00002 | | S | | SM00004 | | S | | 276-299 | | |
| 005 | 20 | PA | | 7-0 | 33-24-13 | D08188 | 5 | | | GD04904 | A.. | 2 | | 150-199 | | |
| 005 | 20 | PA | | 8-0 | 33-24-13 | D08188 | 5 | | | GD04904 | A.. | 2 | | 275 | | |
| 005 | 18 | PA | | 6-0 | 33-24-13 | SM00003 | | S | | SM00005 | | S | | 276-299 | | |
| 006 | 18 | PA | | 7-0 | 33-24-13 | SM00001 | | S | | SM00005 | | S | | 150-199, 275 | | |
| 006 | 18 | PA | | 6-0 | 33-24-13 | SM00004 | | S | | SM00006 | | S | | 276-299 | | |
| 007 | 18 | PA | | 7-0 | 33-24-13 | SM00002 | | S | | SM00006 | | S | | 150-199, 275 | | |
| 007 | 18 | PA | | 4-0 | 33-24-13 | SM00005 | | S | | D05982P | 1 | DK | | 276-299 | | |
| 008 | 20 | PA | | 4-0 | 33-24-13 | SM00001 | | S | | D08190 | 3 | | | 150-199, 275 | | |
| 008 | 18 | PA | | 4-0 | 33-24-13 | SM00006 | | S | | D05982P | 2 | DK | | 276-299 | | |
| 009 | 20 | PA | | 4-0 | 33-24-13 | SM00002 | | S | | D08190 | 4 | | | 150-199, 275 | | |
| 010 | 20 | PA | | 5-0 | 33-24-13 | GD04904 | A.. | 2 | | D08190 | 5 | | | 150-199 | | |
| 010 | 20 | PA | | 6-0 | 33-24-13 | GD04904 | A.. | 2 | | D08190 | 5 | | | 275 | | |
| 013 | 20 | PA | | 3-0 | 33-24-13 | SM00005 | | S | | D08192 | 3 | | | 150-199, 275 | | |
| 014 | 20 | PA | | 3-0 | 33-24-13 | SM00006 | | S | | D08192 | 4 | | | 150-199, 275 | | |
| 015 | 20 | PA | | 5-0 | 33-24-13 | GD04904 | A.. | 2 | | D08192 | 5 | | | 150-199, 275 | | |
| 016 | 18 | PA | | 7-0 | 33-24-13 | SM00005 | | S | | SM00009 | | S | | 150-199, 275 | | |
| 017 | 18 | PA | | 7-0 | 33-24-13 | SM00006 | | S | | SM00010 | | S | | 150-199, 275 | | |
| 018 | 20 | PA | | 4-0 | 33-24-13 | SM00005 | | S | | D08194 | 3 | | | 150-199, 275 | | |
| 019 | 20 | PA | | 4-0 | 33-24-13 | SM00006 | | S | | D08194 | 4 | | | 150-199, 275 | | |
| 020 | 20 | PA | | 4-0 | 33-24-13 | GD01764 | A.. | 2 | | D08194 | 5 | | | 150-199 | | |
| 020 | 20 | PA | | 5-0 | 33-24-13 | GD01764 | A.. | 2 | | D08194 | 5 | | | 275 | | |
| 023 | 20 | PA | | 3-0 | 33-24-13 | SM00009 | | S | | D08196 | 3 | | | 150-199, 275 | | |
| 024 | 20 | PA | | 3-0 | 33-24-13 | SM00010 | | S | | D08196 | 4 | | | 150-199, 275 | | |
| 025 | 20 | PA | | 5-0 | 33-24-13 | GD01760 | A.. | 2 | | D08196 | 5 | | | 150-199 | | |
| 025 | 20 | PA | | 6-0 | 33-24-13 | GD01760 | A.. | 2 | | D08196 | 5 | | | 275 | | |
| 026 | 18 | PA | | 3-0 | 33-24-13 | SM00009 | | S | | D05982P | 1 | DK | | 150-199 | | |
| 026 | 18 | PA | | 4-0 | 33-24-13 | SM00009 | | S | | D05982P | 1 | DK | | 275 | | |

WIRE LIST

D280T132

91-21-11

Section W2060

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-----------------------------------|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|----|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2064 | 286T2064 | | | CENTER PSU MOD (continued) | | | | | | | | | | | | | |
| 027 | 18 | | PA | | 3-0 | 33-24-13 | SM00010 | | | | | | S | D05982P | 2 | DK | 150-199 |
| 027 | 18 | | PA | | 4-0 | 33-24-13 | SM00010 | | | | | | S | D05982P | 2 | DK | 275 |
| 103 | 20 | | PA | | 3-0 | 33-24-13 | D08188 | | 3 | | | | | SM00002 | | S | 276-299 |
| 104 | 20 | | PA | | 3-0 | 33-24-13 | D08188 | | 4 | | | | | SM00001 | | S | 276-299 |
| 105 | 20 | | PA | | 8-0 | 33-24-13 | D08188 | | 5 | | | | | GD04904 | A.. | 2 | 276-299 |
| 113 | 20 | | PA | | 4-0 | 33-24-13 | D08190 | | 3 | | | | | SM00002 | | S | 276-299 |
| 114 | 20 | | PA | | 4-0 | 33-24-13 | D08190 | | 4 | | | | | SM00001 | | S | 276-299 |
| 115 | 20 | | PA | | 6-0 | 33-24-13 | D08190 | | 5 | | | | | GD04904 | A.. | 2 | 276-299 |
| 123 | 20 | | PA | | 3-0 | 33-24-13 | D08192 | | 3 | | | | | SM00004 | | S | 276-299 |
| 124 | 20 | | PA | | 3-0 | 33-24-13 | D08192 | | 4 | | | | | SM00003 | | S | 276-299 |
| 125 | 20 | | PA | | 5-0 | 33-24-13 | D08192 | | 5 | | | | | GD04904 | A.. | 2 | 276-299 |
| 133 | 20 | | PA | | 4-0 | 33-24-13 | D08194 | | 3 | | | | | SM00004 | | S | 276-299 |
| 134 | 20 | | PA | | 4-0 | 33-24-13 | D08194 | | 4 | | | | | SM00003 | | S | 276-299 |
| 135 | 20 | | PA | | 5-0 | 33-24-13 | D08194 | | 5 | | | | | GD01764 | A.. | 2 | 276-299 |
| 143 | 20 | | PA | | 3-0 | 33-24-13 | D08196 | | 3 | | | | | SM00006 | | S | 276-299 |
| 144 | 20 | | PA | | 3-0 | 33-24-13 | D08196 | | 4 | | | | | SM00005 | | S | 276-299 |
| 145 | 20 | | PA | | 6-0 | 33-24-13 | D08196 | | 5 | | | | | GD01760 | A.. | 2 | 276-299 |
| 201B | 22 | | PB | A | 3-0 | 23-31-16 | D05982P | | 3 | | | | | SM00012 | | S | 150-199 |
| 201B | 22 | | PB | A | 4-0 | 23-31-16 | D05982P | | 3 | | | | | SM00012 | | S | 275 |
| 201B | 22 | | PB | IA | 3-0 | 23-31-16 | D08186J | | 3 | | | | | SM00102 | | S | 276-299 |
| 201R | 22 | | PB | A | 0-0 | 23-31-16 | D05982P | | 4 | | | | | SM00011 | | S | 150-199, 275 |
| 201R | 22 | | PB | IA | 0-0 | 23-31-16 | D08186J | | 4 | | | | | SM00101 | | S | 276-299 |
| 202B | 22 | | PB | IB | 3-0 | 23-31-16 | D08188 | | 2 | | | | | SM00102 | | S | 276-299 |
| 202R | 22 | | PB | IB | 0-0 | 23-31-16 | D08188 | | 1 | | | | | SM00101 | | S | 276-299 |
| 203B | 22 | | PB | K | 3-0 | 23-31-16 | D08196 | | 2 | | | | | SM00012 | | S | 150-199, 275 |
| 203B | 22 | | PB | IC | 7-0 | 23-31-16 | SM00102 | | | S | | | | SM00104 | | S | 276-299 |
| 203R | 22 | | PB | K | 0-0 | 23-31-16 | D08196 | | 1 | | | | | SM00011 | | S | 150-199, 275 |
| 203R | 22 | | PB | IC | 0-0 | 23-31-16 | SM00101 | | | S | | | | SM00103 | | S | 276-299 |
| 204B | 22 | | PB | C | 7-0 | 23-31-16 | SM00012 | | | S | | | | SM00016 | | S | 150-199, 275 |
| 204B | 22 | | PB | ID | 4-0 | 23-31-16 | D08190 | | 2 | | | | | SM00102 | | S | 276-299 |
| 204R | 22 | | PB | C | 0-0 | 23-31-16 | SM00011 | | | S | | | | SM00015 | | S | 150-199, 275 |
| 204R | 22 | | PB | ID | 0-0 | 23-31-16 | D08190 | | 1 | | | | | SM00101 | | S | 276-299 |
| 205B | 22 | | PB | D | 4-0 | 23-31-16 | D08194 | | 2 | | | | | SM00016 | | S | 150-199, 275 |
| 205B | 22 | | PB | IE | 6-0 | 23-31-16 | SM00104 | | | S | | | | SM00106 | | S | 276-299 |
| 205R | 22 | | PB | D | 0-0 | 23-31-16 | D08194 | | 1 | | | | | SM00015 | | S | 150-199, 275 |
| 205R | 22 | | PB | IE | 0-0 | 23-31-16 | SM00103 | | | S | | | | SM00105 | | S | 276-299 |
| 206B | 22 | | PB | IF | 3-0 | 23-31-16 | D08192 | | 2 | | | | | SM00104 | | S | 276-299 |
| 206R | 22 | | PB | IF | 0-0 | 23-31-16 | D08192 | | 1 | | | | | SM00103 | | S | 276-299 |
| 207B | 22 | | PB | F | 3-0 | 23-31-16 | SM00016 | | | S | | | | D08192 | 2 | | 150-199, 275 |

WIRE LIST
D280T132

91-21-11
Section W2060
Page 4
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W2064 | 286T2064 | | | CENTER PSU MOD (continued) | | | | | | | | | | | |
| 207B | 22 | PB | IG | | 4-0 | 23-31-16 | SM00106 | | | | S | D05982P | 3 | | 276-299 |
| 207R | 22 | PB | F | | 0-0 | 23-31-16 | SM00015 | | | | S | D08192 | 1 | | 150-199, 275 |
| 207R | 22 | PB | IG | | 0-0 | 23-31-16 | SM00105 | | | | S | D05982P | 4 | | 276-299 |
| 208B | 22 | PB | G | | 7-0 | 23-31-16 | SM00016 | | | | S | SM00020 | | S | 150-199, 275 |
| 208B | 22 | PB | IH | | 4-0 | 23-31-16 | D08194 | 2 | | | S | SM00104 | | S | 276-299 |
| 208R | 22 | PB | G | | 0-0 | 23-31-16 | SM00015 | | | | S | SM00019 | | S | 150-199, 275 |
| 208R | 22 | PB | IH | | 0-0 | 23-31-16 | D08194 | 1 | | | S | SM00103 | | S | 276-299 |
| 209B | 22 | PB | H | | 4-0 | 23-31-16 | SM00020 | | | | S | D08190 | 2 | | 150-199, 275 |
| 209R | 22 | PB | H | | 0-0 | 23-31-16 | SM00019 | | | | S | D08190 | 1 | | 150-199, 275 |
| 210B | 22 | PB | I | | 3-0 | 23-31-16 | SM00020 | | | | S | D08186J | 3 | | 150-199, 275 |
| 210B | 22 | PB | IJ | | 3-0 | 23-31-16 | D08196 | 2 | | | S | SM00106 | | S | 276-299 |
| 210R | 22 | PB | I | | 0-0 | 23-31-16 | SM00019 | | | | S | D08186J | 4 | | 150-199, 275 |
| 210R | 22 | PB | IJ | | 0-0 | 23-31-16 | D08196 | 1 | | | S | SM00105 | | S | 276-299 |
| 211B | 22 | PB | J | | 4-0 | 23-31-16 | SM00020 | | | | S | D08188 | 2 | | 150-199 |
| 211B | 22 | PB | J | | 3-0 | 23-31-16 | SM00020 | | | | S | D08188 | 2 | | 275 |
| 211R | 22 | PB | J | | 0-0 | 23-31-16 | SM00019 | | | | S | D08188 | 1 | | 150-199, 275 |
| 221B | 22 | PB | AA | | 3-0 | 23-31-16 | D05982P | 5 | | | S | SM00112 | | S | 150-199 |
| 221R | 22 | PB | AA | | 0-0 | 23-31-16 | D05982P | 6 | | | S | SM00111 | | S | 150-199 |
| 223B | 22 | PB | AK | | 3-0 | 23-31-16 | D08196 | 7 | | | S | SM00112 | | S | 150-199 |
| 223R | 22 | PB | AK | | 0-0 | 23-31-16 | D08196 | 6 | | | S | SM00111 | | S | 150-199 |
| 224B | 22 | PB | AC | | 7-0 | 23-31-16 | SM00112 | | | | S | SM00116 | | S | 150-199 |
| 224R | 22 | PB | AC | | 0-0 | 23-31-16 | SM00111 | | | | S | SM00115 | | S | 150-199 |
| 225B | 22 | PB | AD | | 4-0 | 23-31-16 | D08194 | 7 | | | S | SM00116 | | S | 150-199 |
| 225R | 22 | PB | AD | | 0-0 | 23-31-16 | D08194 | 6 | | | S | SM00115 | | S | 150-199 |
| 227B | 22 | PB | AF | | 3-0 | 23-31-16 | SM00116 | | | | S | D08192 | 7 | | 150-199 |
| 227R | 22 | PB | AF | | 0-0 | 23-31-16 | SM00115 | | | | S | D08192 | 6 | | 150-199 |
| 228B | 22 | PB | AG | | 7-0 | 23-31-16 | SM00116 | | | | S | SM00120 | | S | 150-199 |
| 228R | 22 | PB | AG | | 0-0 | 23-31-16 | SM00115 | | | | S | SM00119 | | S | 150-199 |
| 229B | 22 | PB | AH | | 4-0 | 23-31-16 | SM00120 | | | | S | D08190 | 7 | | 150-199 |
| 229R | 22 | PB | AH | | 0-0 | 23-31-16 | SM00119 | | | | S | D08190 | 6 | | 150-199 |
| 230B | 22 | PB | AI | | 3-0 | 23-31-16 | SM00120 | | | | S | D08186J | 5 | | 150-199 |
| 230R | 22 | PB | AI | | 0-0 | 23-31-16 | SM00119 | | | | S | D08186J | 6 | | 150-199 |
| 231B | 22 | PB | AJ | | 3-0 | 23-31-16 | SM00120 | | | | S | D08188 | 7 | | 150-199 |
| 231R | 22 | PB | AJ | | 0-0 | 23-31-16 | SM00119 | | | | S | D08188 | 6 | | 150-199 |
| W2066 | 286T2066 | | | CENTER MID OXYGEN LATCHES STA 654+114-STA 748 | | | | | | | | | | | |
| 001 | 14 | PA | | | 2-0 | 35-21-14 | D05996J | 1 | FN | | | SM00001 | | S | 275 |
| 001 | 14 | PA | | | 3-0 | 35-21-14 | D05996J | 1 | FN | | | SM00001 | | S | 276-299 |
| 002 | 20 | PA | | | 2-0 | 35-21-14 | SM00001 | | | | S | D11118 | 1 | | 275 |

WIRE LIST

D280T132

91-21-11

Section W2060

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2066 | 286T2066 | | | CENTER MID OXYGEN LATCHES STA 654+114-STA 748 (continued) | | | | | | | | | | | |
| 003 | 20 | | PA | | 8-0 | 35-21-14 | D11118 | | | | GD00960 | D.. | 2 | | 275 |
| 003 | 14 | | PA | | 6-0 | 35-21-14 | SM00001 | | S | | SM00003 | | | S | 276-299 |
| 004 | 14 | | PA | | 6-0 | 35-21-14 | SM00001 | | S | | SM00003 | | | S | 275 |
| 005 | 20 | | PA | | 3-0 | 35-21-14 | SM00001 | | S | | D11120 | | 1 | | 275 |
| 005 | 14 | | PA | | 5-0 | 35-21-14 | SM00003 | | S | | SM00005 | | | S | 276-299 |
| 006 | 20 | | PA | | 5-0 | 35-21-14 | D11120 | | 2 | | GD00960 | D.. | 2 | | 275 |
| 007 | 14 | | PA | | 5-0 | 35-21-14 | SM00005 | | S | | D08198P | | 1 | FO | 276-299 |
| 008 | 20 | | PA | | 2-0 | 35-21-14 | SM00003 | | S | | D11122 | | 1 | | 275 |
| 009 | 20 | | PA | | 7-0 | 35-21-14 | D11122 | | 2 | | GD04444 | D.. | 2 | | 275 |
| 010 | 14 | | PA | | 4-0 | 35-21-14 | SM00003 | | S | | SM00005 | | | S | 275 |
| 011 | 20 | | PA | | 3-0 | 35-21-14 | SM00003 | | S | | D11124 | | 1 | | 275 |
| 012 | 20 | | PA | | 4-0 | 35-21-14 | D11124 | | 2 | | GD04444 | D.. | 2 | | 275 |
| 014 | 20 | | PA | | 3-0 | 35-21-14 | SM00005 | | S | | D11126 | | 1 | | 275 |
| 015 | 20 | | PA | | 7-0 | 35-21-14 | D11126 | | 2 | | GD04444 | D.. | 2 | | 275 |
| 016 | 14 | | PA | | 5-0 | 35-21-14 | SM00005 | | S | | D08198P | | 1 | FO | 275 |
| 101 | 20 | | PA | | 3-0 | 35-21-14 | D11118 | | 1 | | SM00001 | | | S | 276-299 |
| 102 | 20 | | PA | | 8-0 | 35-21-14 | D11118 | | 2 | | GD00960 | D.. | 2 | | 276-299 |
| 111 | 20 | | PA | | 4-0 | 35-21-14 | D11120 | | 1 | | SM00001 | | | S | 276-299 |
| 112 | 20 | | PA | | 6-0 | 35-21-14 | D11120 | | 2 | | GD00960 | D.. | 2 | | 276-299 |
| 121 | 20 | | PA | | 3-0 | 35-21-14 | D11122 | | 1 | | SM00003 | | | S | 276-299 |
| 122 | 20 | | PA | | 6-0 | 35-21-14 | D11122 | | 2 | | GD00960 | D.. | 2 | | 276-299 |
| 131 | 20 | | PA | | 4-0 | 35-21-14 | D11124 | | 1 | | SM00003 | | | S | 276-299 |
| 132 | 20 | | PA | | 4-0 | 35-21-14 | D11124 | | 2 | | GD04444 | D.. | 2 | | 276-299 |
| 141 | 20 | | PA | | 3-0 | 35-21-14 | D11126 | | 1 | | SM00005 | | | S | 276-299 |
| 142 | 20 | | PA | | 6-0 | 35-21-14 | D11126 | | 2 | | GD01940 | D.. | 2 | | 276-299 |
| W2068 | 286T2068 | | | CENTER AFT OXYGEN LATCHES STA 1197+092-STA 1273 | | | | | | | | | | | |
| 001 | 14 | | PA | | 2-2 | 35-21-14 | D08200J | | 1 | FN | SM00001 | | | S | 150-199 |
| 001 | 14 | | PA | | 3-0 | 35-21-14 | D08200J | | 1 | FN | SM00001 | | | S | 275-299 |
| 002 | 20 | | PA | | 2-3 | 35-21-14 | SM00001 | | | S | D11128 | | 1 | | 150-199 |
| 002 | 20 | | PA | | 3-0 | 35-21-14 | SM00001 | | | S | D11128 | | 1 | | 275 |
| 003 | 20 | | PA | | 6-10 | 35-21-14 | D11128 | | 2 | | GD04904 | D.. | 2 | | 150-199 |
| 003 | 20 | | PA | | 8-0 | 35-21-14 | D11128 | | 2 | | GD04904 | D.. | 2 | | 275 |
| 003 | 14 | | PA | | 6-0 | 35-21-14 | SM00001 | | | S | SM00003 | | | S | 276-299 |
| 004 | 14 | | PA | | 5-3 | 35-21-14 | SM00001 | | | S | SM00003 | | | S | 150-199 |
| 004 | 14 | | PA | | 6-0 | 35-21-14 | SM00001 | | | S | SM00003 | | | S | 275 |
| 005 | 20 | | PA | | 2-1 | 35-21-14 | SM00001 | | | S | D11130 | | 1 | | 150-199 |
| 005 | 20 | | PA | | 4-0 | 35-21-14 | SM00001 | | | S | D11130 | | 1 | | 275 |
| 005 | 14 | | PA | | 5-0 | 35-21-14 | SM00003 | | | S | SM00005 | | | S | 276-299 |

WIRE LIST

D280T132

91-21-11

Section W2060

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|-------|--|----------|---------|---------|-------|------|------|---------|-------|-------------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W2068 | 286T2068 | | | CENTER AFT OXYGEN LATCHES STA 1197+092-STA 1273 (continued) | | | | | | | | | | | |
| 006 | 20 | PA | | 4-3 | 35-21-14 | D11130 | | 2 | | | GD04904 | D.. | 2 | | 150-199 |
| 006 | 20 | PA | | 6-0 | 35-21-14 | D11130 | | 2 | | | GD04904 | D.. | 2 | | 275 |
| 007 | 14 | PA | | 5-0 | 35-21-14 | SM00005 | | | S | | D06004P | 1 | FO | | 276-299 |
| 008 | 20 | PA | | 2-2 | 35-21-14 | SM00003 | | | S | | D11132 | 1 | | | 150-199 |
| 008 | 20 | PA | | 3-0 | 35-21-14 | SM00003 | | | S | | D11132 | 1 | | | 275 |
| 009 | 20 | PA | | 4-2 | 35-21-14 | D11132 | | 2 | | | GD04904 | D.. | 2 | | 150-199 |
| 009 | 20 | PA | | 6-0 | 35-21-14 | D11132 | | 2 | | | GD04904 | D.. | 2 | | 275 |
| 010 | 14 | PA | | 4-7 | 35-21-14 | SM00003 | | | S | | SM00005 | | S | | 150-199 |
| 010 | 14 | PA | | 5-0 | 35-21-14 | SM00003 | | | S | | SM00005 | | S | | 275 |
| 011 | 20 | PA | | 2-1 | 35-21-14 | SM00003 | | | S | | D11134 | 1 | | | 150-199 |
| 011 | 20 | PA | | 4-0 | 35-21-14 | SM00003 | | | S | | D11134 | 1 | | | 275 |
| 012 | 20 | PA | | 3-1 | 35-21-14 | D11134 | | 2 | | | GD01764 | D.. | 2 | | 150-199 |
| 012 | 20 | PA | | 5-0 | 35-21-14 | D11134 | | 2 | | | GD01764 | D.. | 2 | | 275 |
| 014 | 20 | PA | | 1-10 | 35-21-14 | D11136 | | 1 | | | SM00005 | | S | | 150-199 |
| 014 | 20 | PA | | 3-0 | 35-21-14 | D11136 | | 1 | | | SM00005 | | S | | 275 |
| 015 | 20 | PA | | 4-5 | 35-21-14 | D11136 | | 2 | | | GD01760 | D.. | 2 | | 150-199 |
| 015 | 20 | PA | | 6-0 | 35-21-14 | D11136 | | 2 | | | GD01760 | D.. | 2 | | 275 |
| 016 | 14 | PA | | 2-5 | 35-21-14 | SM00005 | | | S | | D06004P | 1 | FO | | 150-199 |
| 016 | 14 | PA | | 5-0 | 35-21-14 | SM00005 | | | S | | D06004P | 1 | FO | | 275 |
| 101 | 20 | PA | | 3-0 | 35-21-14 | D11128 | | 1 | | | SM00001 | | S | | 276-299 |
| 102 | 20 | PA | | 7-0 | 35-21-14 | D11128 | | 2 | | | GD04904 | D.. | 2 | | 276-299 |
| 111 | 20 | PA | | 4-0 | 35-21-14 | D11130 | | 1 | | | SM00001 | | S | | 276-299 |
| 112 | 20 | PA | | 5-0 | 35-21-14 | D11130 | | 2 | | | GD04904 | D.. | 2 | | 276-299 |
| 121 | 20 | PA | | 3-0 | 35-21-14 | D11132 | | 1 | | | SM00003 | | S | | 276-299 |
| 122 | 20 | PA | | 6-0 | 35-21-14 | D11132 | | 2 | | | GD04904 | D.. | 2 | | 276-299 |
| 131 | 20 | PA | | 4-0 | 35-21-14 | D11134 | | 1 | | | SM00003 | | S | | 276-299 |
| 132 | 20 | PA | | 4-0 | 35-21-14 | D11134 | | 2 | | | GD01764 | D.. | 2 | | 276-299 |
| 141 | 20 | PA | | 3-0 | 35-21-14 | D11136 | | 1 | | | SM00005 | | S | | 276-299 |
| 142 | 20 | PA | | 6-0 | 35-21-14 | D11136 | | 2 | | | GD01760 | D.. | 2 | | 276-299 |

WIRE LIST

D280T132

91-21-11

Section W2060

Page 7 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|-----------------------------------|-------|----------|-------------|------|------|-----------|--------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2108 | 286T2108 | | | P31 TO P87-L1-POWER FEEDER | | | | | | | | | | | |
| 001 | 08 | PA | | | 13-0 | 24-51-13 | K00119 | A2 | E | | TB5196 | 1 | E | | 278-299 |
| 002 | 08 | PA | | | 12-10 | 24-51-13 | K00119 | B2 | E | | TB5196 | 2 | E | | 278-299 |
| 003 | 08 | PA | | | 12-10 | 24-51-13 | K00119 | C2 | E | | TB5196 | 3 | E | | 278-299 |

WIRE LIST
D280T132

91-21-11
Section W2100
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2110 | 286T2110 | | | P87-L1-POWER DISTRIBUTION | | | | | | | | | | | |
| 001 | 12 | PA | | 7-4 | 24-51-13 | C00379 | A1 | D | * | TB5196 | 1 | E | | 278-299 | |
| 002 | 12 | PA | | 7-4 | 24-51-13 | C00408 | B1 | D | * | TB5196 | 2 | E | | 278-299 | |
| 003 | 12 | PA | | 7-4 | 24-51-13 | C00379 | C1 | D | * | TB5196 | 3 | E | | 278-299 | |
| 007 | 14 | PA | | 4-1 | 24-51-13 | L01261 | | 1 | C | TB5196 | 2 | E | | 278-299 | |
| 008 | 14 | PA | | 2-0 | 24-51-13 | L01261 | | 2 | C | GDX0004 | A.. | F | | 278-299 | |
| 012 | 12 | PA | | 1-4 | 24-51-13 | C00379 | A1 | D | * | C00408 | A1 | D | * | 278-299 | |
| 014 | 12 | PA | | 1-4 | 24-51-13 | C00379 | C1 | D | * | C00408 | C1 | D | * | 278-299 | |
| 015 | 12 | PA | | 2-3 | 24-51-13 | C00408 | A1 | D | * | C00409 | A1 | D | | 278-299 | |
| 016 | 12 | PA | | 2-3 | 24-51-13 | C00408 | B1 | D | * | C00409 | B1 | D | | 278-299 | |
| 017 | 12 | PA | | 2-3 | 24-51-13 | C00408 | C1 | D | * | C00409 | C1 | D | | 278-299 | |
| W2112 | 286T2112 | | | P87-L2-MISC ELECTRICAL PANEL | | | | | | | | | | | |
| 007 | 20 | PA | | 7-0 | 21-45-24 | C00408 | A2 | D | | D07126J | 12 | | | 278-299 | |
| 008 | 20 | PA | | 7-0 | 21-45-24 | C00408 | B2 | D | | D07126J | 13 | | | 278-299 | |
| 009 | 20 | PA | | 7-0 | 21-45-24 | C00408 | C2 | D | | D07126J | 14 | | | 278-299 | |
| 010 | 20 | PA | | 7-0 | 21-45-24 | C00409 | A2 | D | | D07126J | 15 | | | 278-299 | |
| 011 | 20 | PA | | 6-0 | 21-45-24 | C00409 | B2 | D | | D07126J | 16 | | | 278-299 | |
| 012 | 20 | PA | | 7-0 | 21-45-24 | C00409 | C2 | D | | D07126J | 17 | | | 278-299 | |
| 013 | 20 | UA | | 2-0 | 21-45-24 | GDX0001 | S.. | 2 | | D72034 | REF | | FA | 278-299 | |
| 016 | 24 | PK | | 5-0 | 21-45-24 | D72034 | X1 | | | D07126J | 2 | | | 278-299 | |
| 017 | 24 | PK | | 5-0 | 21-45-24 | D72034 | X2 | | | D07126J | 1 | | | 278-299 | |
| 201B | 18 | PR | A | 9-0 | 21-45-24 | C00379 | C2 | D | | D72034 | D2 | | | 278-299 | |
| 201R | 18 | PR | A | 0-0 | 21-45-24 | C00379 | A2 | D | | D72034 | C2 | | | 278-299 | |
| 201Z | | | A | 0-0 | 21-45-24 | C00379 | DED | | | D72034 | REF | | FA | 278-299 | |
| 202B | 18 | PR | B | 5-0 | 21-45-24 | D07126J | | 23 | | D72034 | D1 | | | 278-299 | |
| 202R | 18 | PR | B | 0-0 | 21-45-24 | D07126J | | 21 | | D72034 | C1 | | | 278-299 | |
| 202Z | | | B | 0-0 | 21-45-24 | D07126J | | 22 | | D72034 | REF | | FA | 278-299 | |

WIRE LIST

D280T132

91-21-11

Section W2110

Page 1 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|----------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2214 | 286T2214 | | | FLIGHT DECK SECURITY DOOR | | | | | | | | | | | |
| 003 | 24 | | PK | 11-6 | 52-51-11 | D05000P | | 18 | | | SP00837 | | 9 | | 050-099, 150-163, 166-199, 275-299 |
| 009 | 24 | | PK | 14-2 | 52-51-11 | D00874 | | 7 | | | SP00843 | | 9 | | 050-099, 150-163, 166-199, 275-299 |
| 010 | 24 | | PK | 14-2 | 52-51-11 | D00874 | | 9 | | | SP00847 | | 9 | | 050-099, 150-163, 166-199, 275-299 |
| 013 | 20 | | PA | 10-7 | 52-51-11 | D30013 | | = 1 | | | GD00369 | D.. | 1A | | 050-099, 150-163, 166-199, 275-299 |
| 019 | 24 | | PK | 14-2 | 52-51-11 | D00874 | | 12 | | | SP00853 | | 9 | | 050-099, 150-163, 166-199, 275-299 |
| 021 | 24 | | PK | 14-2 | 52-51-11 | D00874 | | 14 | | | SP00849 | | 9 | | 050-099, 150-163, 166-199, 275-299 |
| A-A | | | | 11-8 | 52-51-11 | M12096 | | 2 | | | SP00837 | | 9 | | 050-099, 150-163, 166-199, 275-299 |
| A-B | | | | 8-6 | 52-51-11 | M12096 | | 5 | | | GD00369 | S.. | 1A | | 050-099, 150-163, 166-199, 275-299 |
| A-C | | | | 8-6 | 52-51-11 | M12096 | | 8 | | | GD00369 | D.. | 1A | | 050-099, 150-163, 166-199, 275-299 |
| A-D | | | | 17-11 | 52-51-11 | M12096 | | 6 | | | D30003 | = 1 | | | 050-099, 150-163, 166-199, 275-299 |
| A-E | | | | 11-8 | 52-51-11 | M12096 | | 4 | | | SP00841 | | 9 | | 050-099, 150-163, 166-199, 275-299 |
| A-F | | | | 3-6 | 52-51-11 | M12093 | | 8 | | | SP00837 | | 9 | | 050-099, 150-163, 166-199, 275-299 |
| A-G | | | | 5-0 | 52-51-11 | M12093 | | 7 | | | D30009 | = 1 | | | 050-099, 150-163, 166-199, 275-299 |
| A-H | | | | 5-0 | 52-51-11 | M12093 | | 15 | | | D30011 | = 1 | | | 050-099, 150-163, 166-199, 275-299 |
| A-J | | | | 3-6 | 52-51-11 | M12093 | | 10 | | | SP00847 | | 9 | | 050-099, 150-163, 166-199, 275-299 |
| A-K | | | | 3-6 | 52-51-11 | M12093 | | 21 | | | SP00849 | | 9 | | 050-099, 150-163, 166-199, 275-299 |
| A-L | | | | 3-6 | 52-51-11 | M12093 | | 19 | | | SP00853 | | 9 | | 050-099, 150-163, 166-199, 275-299 |
| A-M | | | | 6-3 | 52-51-11 | M12093 | | 1 | | | GD00434 | D.. | 2 | | 050-099, 150-163, 166-199, 275-299 |
| A-N | | | | 6-3 | 52-51-11 | M12093 | | 2 | | | GD00369 | S.. | 1A | | 050-099, 150-163, 166-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W2210
Page 1
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|--|-------|----------|-------------|------|------|-----------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2214 | 286T2214 | | | FLIGHT DECK SECURITY DOOR (continued) | | | | | | | | | | | |
| A-P | | | | | 3-6 | 52-51-11 | M12093 | | 9 | | SP00843 | | 9 | | 050-099, 150-163, 166-199, 275-299 |
| A-Q | | | | | 3-6 | 52-51-11 | M12093 | | 23 | | SP00841 | | 9 | | 050-099, 150-163, 166-199, 275-299 |

WIRE LIST
D280T132

91-21-11
Section W2210
Page 2 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3000 | 286T3000 | | | CREW REST UPPER BUNK CONSOLE. | | | | | | | | | | | |
| 001 | 22 | | PA | | 6-0 | 33-24-13 | D06890J | | | | D06125P | 8 | | | 050-099, 162-199 |
| 002 | 22 | | PA | | 6-0 | 33-24-13 | D06890J | | | | D06125P | 9 | | | 050-099, 162-199 |
| 003 | 20 | | PA | | 6-0 | 33-24-13 | D06890J | | | 10 | D06125P | 10 | | | 050-099, 162-199 |
| 004 | 20 | | PA | | 2-0 | 35-21-14 | D06890J | | | 3 | SM00001 | | S | | 050-099, 162-199 |
| 005 | 20 | | PA | | 2-0 | 35-21-14 | D06890J | | | 4 | SM00002 | | S | | 050-099, 162-199 |
| 006 | 20 | | PA | | 5-0 | 35-21-14 | D06125P | | | 6 | SM00001 | | S | | 050-099, 162-199 |
| 007 | 20 | | PA | | 5-0 | 35-21-14 | D06125P | | | 7 | SM00002 | | S | | 050-099, 162-199 |
| 008 | 20 | | PA | | 2-0 | 35-21-14 | D12224 | | | 1 | SM00001 | | S | | 050-099, 162-199 |
| 009 | 20 | | PA | | 2-0 | 35-21-14 | D12224 | | | 2 | SM00002 | | S | | 050-099, 162-199 |
| 010 | 20 | | PA | | 3-0 | 23-34-15 | D12232 | | | 7 | SM00003 | | S | | 050-099, 162-199 |
| 011 | 20 | | PA | | 4-0 | 23-34-15 | D12232 | | | 3 | L01183 | | =P | C | 050-099, 162-199 |
| 012 | 20 | | PA | | 3-0 | 23-34-15 | L01183 | | =G | | C | | S | | 050-099, 162-199 |
| 013 | 20 | | PA | | 4-0 | 23-34-15 | D12232 | | | 4 | D06890J | | 2 | | 050-099, 162-199 |
| 014 | 20 | | PA | | 3-0 | 23-34-15 | D06890J | | | 1 | SM00003 | | S | | 050-099, 162-199 |
| 201B | 16 | | PB | IA | 6-0 | 23-34-15 | D06125P | | | 3 | FL | | 3 | FM | 050-099, 162-199 |
| 201R | 16 | | PB | IA | 0-0 | 23-34-15 | D06125P | | | 2 | FL | | 2 | FM | 050-099, 162-199 |
| 301B | 24 | | PM | MA | 6-0 | 23-34-15 | D06125P | | | 4 | | | 4 | | 050-099, 162-199 |
| 301R | 24 | | PM | MA | 0-0 | 23-34-15 | D06125P | | | 5 | | | 5 | | 050-099, 162-199 |
| 301Y | 24 | | PM | MA | 0-0 | 23-34-15 | D06125P | | | 1 | | | 1 | | 050-099, 162-199 |
| W3002 | 286T3002 | | | CREW REST RIGHT HAND PARTITION | | | | | | | | | | | |
| 001 | 22 | | PA | | 3-0 | 33-24-13 | D06890P | | | 8 | L01190 | | NS | C | * 050-099, 162-199 |
| 002 | 22 | | PA | | 3-0 | 33-24-13 | D06890P | | | 9 | L01190 | | FSB | C | * 050-099, 162-199 |
| 003 | 20 | | PA | | 3-0 | 33-24-13 | D06890P | | | 10 | L01190 | | GND | C | * 050-099, 162-199 |
| 004 | 22 | | PA | | 4-0 | 33-24-13 | D06892P | | | 8 | L01190 | | NS | C | * 050-099, 162-199 |
| 005 | 22 | | PA | | 4-0 | 33-24-13 | D06892P | | | 9 | L01190 | | FSB | C | * 050-099, 162-199 |
| 006 | 20 | | PA | | 4-0 | 33-24-13 | D06892P | | | 10 | L01190 | | GND | C | * 050-099, 162-199 |
| 007 | 20 | | PA | | 5-0 | 35-21-14 | D06890P | | | 3 | D06892P | | 3 | | 050-099, 162-199 |
| 008 | 20 | | PA | | 5-0 | 35-21-14 | D06890P | | | 4 | D06892P | | 4 | | 050-099, 162-199 |
| 009 | 20 | | PA | | 5-0 | 23-34-15 | D06890P | | | 1 | D06892P | | 1 | | 050-099, 162-199 |
| 010 | 20 | | PA | | 5-0 | 23-34-15 | D06890P | | | 2 | D06892P | | 2 | | 050-099, 162-199 |
| W3004 | 286T3004 | | | CREW REST LOWER BUNK CONSOLE. | | | | | | | | | | | |
| 001 | 22 | | PA | | 3-0 | 33-24-13 | D06892J | | | 8 | L01189 | | 1 | C | 050-099, 162-199 |
| 002 | 22 | | PA | | 3-0 | 33-24-13 | D06892J | | | 9 | L01189 | | 3 | C | 050-099, 162-199 |
| 003 | 20 | | PA | | 3-0 | 33-24-13 | D06892J | | | 10 | L01189 | | 2 | C | 050-099, 162-199 |
| 004 | 20 | | PA | | 2-0 | 35-21-14 | D12222 | | | 1 | D06892J | | 3 | | 050-099, 162-199 |
| 005 | 20 | | PA | | 2-0 | 35-21-14 | D12222 | | | 2 | D06892J | | 4 | | 050-099, 162-199 |
| 006 | 20 | | PA | | 2-0 | 23-34-15 | D06892J | | | 1 | L01184 | | =G | C | 050-099, 162-199 |

WIRE LIST
D280T132

91-21-11
Section W3000
Page 1
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|-------------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3004 | 286T3004 | | | CREW REST LOWER BUNK CONSOLE. (continued) | | | | | | | | | | | |
| 007 | 20 | | PA | | 2-0 | 23-34-15 | D06892J | | 2 | | L01184 | =P | C | | 050-099, 162-199 |
| W3006 | 286T3006 | | | CREW REST AMENITY MODULE. | | | | | | | | | | | |
| 001 | 20 | | PA | | 4-0 | 33-26-21 | SM00006 | | | S | L01192 | A | Z1 | | 050-099, 162-166 |
| 001 | 20 | | PA | | 4-0 | 33-26-21 | SM00006 | | | S | L01192 | A+ | Z1 | * | 167-199 |
| 002 | 20 | | PA | | 5-0 | 33-26-21 | L01191 | | A | Z1 | SM00006 | | S | | 050-099, 162-166 |
| 002 | 20 | | PA | | 5-0 | 33-26-21 | L01191 | | A+ | Z1 | SM00006 | | S | * | 167-199 |
| 003 | 20 | | PA | | 4-0 | 33-26-21 | SM00007 | | | S | L01192 | B | Z1 | | 050-099, 162-166 |
| 003 | 20 | | PA | | 4-0 | 33-26-21 | SM00007 | | | S | L01192 | A- | Z1 | * | 167-199 |
| 004 | 20 | | PA | | 5-0 | 33-26-21 | L01191 | | B | Z1 | SM00007 | | S | | 050-099, 162-166 |
| 004 | 20 | | PA | | 5-0 | 33-26-21 | L01191 | | A- | Z1 | SM00007 | | S | * | 167-199 |
| 005 | 20 | | PA | | 7-0 | 33-51-13 | D06109P | | 13 | | L01193 | | 1 | C | 050-099, 162-199 |
| 006 | 20 | | PA | | 7-0 | 33-51-13 | D06109P | | 14 | | L01193 | | 2 | C | 050-099, 162-199 |
| 007 | 22 | | PA | | 7-0 | 33-22-33 | D06109P | | 9 | | L01187 | =P | C | * | 050-099, 162-199 |
| 008 | 22 | | PA | | 8-0 | 33-22-33 | S00809 | | C | Z1 | L01187 | =P | C | * | 050-099, 162-199 |
| 009 | 22 | | PA | | 4-0 | 33-22-33 | S00809 | | NO | Z1 | L01188 | =P | C | | 050-099, 162-199 |
| 010 | 22 | | PA | | 7-0 | 33-22-33 | L01188 | | =G | C | L01187 | =G | C | * | 050-099, 162-199 |
| 011 | 22 | | PA | | 7-0 | 33-22-33 | D06109P | | 10 | | L01187 | =G | C | * | 050-099, 162-199 |
| 012 | 24 | | PK | | 2-0 | 23-34-15 | D12230 | | D | | D12230 | E | | | 050-099, 162-199 |
| 013 | 20 | | PA | | 8-0 | 23-34-15 | D12230 | | B | | D06109P | | 16 | | 050-099, 162-199 |
| 016 | 22 | | PA | | 3-0 | 23-42-11 | D12236 | | A1 | | SM00004 | | S | | 050-099, 162-199 |
| 017 | 22 | | PA | | 4-0 | 23-42-11 | D12234 | | A1 | | D06109P | | 18 | | 050-099, 162-199 |
| 018 | 20 | | PA | | 3-0 | 23-42-11 | D12234 | | A2 | | SM00001 | | S | | 050-099, 162-199 |
| 019 | 22 | | PA | | 3-0 | 23-42-11 | D12234 | | X1 | | SM00002 | | S | | 050-099, 162-199 |
| 01CO | | | | A | 0-0 | 23-34-15 | D06109P | | =C15 | | D12228 | =CF | | | 050-099, 162-199 |
| 01CX | | | | A | 8-0 | 23-34-15 | D06109P | | 15 | | D12228 | F | | | 050-099, 162-199 |
| 020 | 22 | | PA | | 3-0 | 23-42-11 | D12234 | | C1 | | SM00003 | | S | | 050-099, 162-199 |
| 021 | 20 | | PA | | 2-0 | 23-42-11 | D06111P | | 1 | | SM00001 | | S | | 050-099, 162-199 |
| 022 | 22 | | PA | | 2-0 | 23-42-11 | D06111P | | 2 | | SM00002 | | S | | 050-099, 162-199 |
| 023 | 20 | | PA | | 4-0 | 23-42-11 | D12236 | | C1 | | D06109P | | 17 | | 050-099, 162-199 |
| 024 | 22 | | PA | | 2-0 | 23-42-11 | D06111P | | 5 | | SM00003 | | S | | 050-099, 162-199 |
| 025 | 22 | | PA | | 3-0 | 23-42-11 | D12236 | | X1 | | SM00002 | | S | | 050-099, 162-199 |
| 026 | 22 | | PA | | 3-0 | 23-42-11 | D12236 | | A2 | | SM00002 | | S | | 050-099, 162-199 |
| 027 | 20 | | PA | | 3-0 | 23-42-11 | D12236 | | X2 | | SM00001 | | S | | 050-099, 162-199 |
| 028 | 20 | | PA | | 3-0 | 23-42-11 | D12234 | | X2 | | SM00001 | | S | | 050-099, 162-199 |
| 029 | 20 | | PA | | 3-0 | 23-42-11 | D06111P | | 6 | | SM00005 | | S | | 050-099, 162-199 |
| 030 | 20 | | PA | | 6-0 | 23-42-11 | B00416 | | NO | Z1 | SM00005 | | S | | 050-099, 162-199 |
| 031 | 20 | | PA | | 6-0 | 23-42-11 | B00416 | | B | Z1 | SM00005 | | S | | 050-099, 162-164 |
| 031 | 20 | | PA | | 6-0 | 23-42-11 | B00416 | | B+ | Z1 | SM00005 | | S | * | 165-199 |

WIRE LIST

D280T132

91-21-11

Section W3000

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3006 | 286T3006 | | | CREW REST AMENITY MODULE. (continued) | | | | | | | | | | | |
| 032 | 20 | | PA | | 3-0 | 23-42-11 | B00417 | | B | Z1 | | | | S | 050-099, 162-164 |
| 032 | 20 | | PA | | 3-0 | 23-42-11 | B00417 | | B+ | Z1 | * | | | S | 165-199 |
| 033 | 20 | | PA | | 3-0 | 23-42-11 | B00417 | | NO | Z1 | | | | S | 050-099, 162-199 |
| 034 | 22 | | PA | | 6-0 | 23-42-11 | B00416 | | A | Z1 | | | | S | 050-099, 162-164 |
| 034 | 22 | | PA | | 6-0 | 23-42-11 | B00416 | | A+ | Z1 | * | | | S | 165-199 |
| 035 | 22 | | PA | | 7-0 | 23-42-11 | B00416 | | C | Z1 | | | | S | 050-099, 162-199 |
| 036 | 22 | | PA | | 3-0 | 23-42-11 | B00417 | | A | Z1 | | | | S | 050-099, 162-164 |
| 036 | 22 | | PA | | 3-0 | 23-42-11 | B00417 | | A+ | Z1 | * | | | S | 165-199 |
| 037 | 22 | | PA | | 4-0 | 23-42-11 | B00417 | | C | Z1 | | | | S | 050-099, 162-199 |
| 038 | 20 | | PA | | 4-0 | 33-26-21 | SM00006 | | | S | | | 11 | | 050-099, 162-199 |
| 039 | 20 | | PA | | 4-0 | 33-26-21 | SM00007 | | | S | | | 12 | | 050-099, 162-199 |
| 040 | 24 | | PK | | 1-0 | 23-42-11 | B00416 | = A+ | Z1 | | | B+ | Z1 | * | 165-166 |
| 040 | 24 | | PK | | 1-0 | 23-42-11 | B00416 | A- | Z1 | | | B+ | Z1 | * | 167-199 |
| 041 | 24 | | PK | | 1-0 | 23-42-11 | B00416 | = B+ | Z1 | | | A+ | Z1 | * | 165-166 |
| 041 | 24 | | PK | | 1-0 | 23-42-11 | B00416 | B- | Z1 | | | A+ | Z1 | * | 167-199 |
| 042 | 24 | | PK | | 1-0 | 23-42-11 | B00417 | = A+ | Z1 | | | B+ | Z1 | * | 165-166 |
| 042 | 24 | | PK | | 1-0 | 23-42-11 | B00417 | A- | Z1 | | | B+ | Z1 | * | 167-199 |
| 043 | 24 | | PK | | 1-0 | 23-42-11 | B00417 | = B+ | Z1 | | | A+ | Z1 | * | 165-166 |
| 043 | 24 | | PK | | 1-0 | 23-42-11 | B00417 | B- | Z1 | | | A+ | Z1 | * | 167-199 |
| 044 | 20 | | PA | | 1-0 | 33-26-21 | L01192 | A+ | Z1 | * | | B+ | Z1 | | 167-199 |
| 045 | 20 | | PA | | 1-0 | 33-26-21 | L01192 | B- | Z1 | | | A- | Z1 | * | 167-199 |
| 046 | 20 | | PA | | 1-0 | 33-26-21 | L01191 | A+ | Z1 | * | | B+ | Z1 | | 167-199 |
| 047 | 20 | | PA | | 1-0 | 33-26-21 | L01191 | B- | Z1 | | | A- | Z1 | * | 167-199 |
| 201B | 20 | | PB | IA | 8-0 | 23-34-15 | D12228 | | B | | | | 2 | | 050-099, 162-199 |
| 201R | 20 | | PB | IA | 0-0 | 23-34-15 | D12228 | | A | | | | 1 | | 050-099, 162-199 |
| 301B | 22 | | PC | MA | 5-0 | 21-66-11 | D06109P | | 8 | | | | A | | 050-099, 162-199 |
| 301R | 22 | | PC | MA | 0-0 | 21-66-11 | D06109P | | 7 | | | | B | | 050-099, 162-199 |
| 301Y | 22 | | PC | MA | 0-0 | 21-66-11 | D06109P | | 6 | | | | C | | 050-099, 162-199 |
| 302B | 24 | | PM | MB | 8-0 | 23-34-15 | D12228 | | E | | | | 5 | | 050-099, 162-199 |
| 302R | 24 | | PM | MB | 0-0 | 23-34-15 | D12228 | | D | | | | 4 | | 050-099, 162-199 |
| 302Y | 24 | | PM | MB | 0-0 | 23-34-15 | D12228 | | C | | | | 3 | | 050-099, 162-199 |
| 401B | 24 | | PY | QA | 6-0 | 23-42-11 | D06111P | | 37 | | | | 3 | | 050-099, 162-199 |
| 401G | 24 | | PY | QA | 0-0 | 23-42-11 | D06111P | | 39 | | | CAP | Y | | 050-099, 162-199 |
| 401R | 24 | | PY | QA | 0-0 | 23-42-11 | D06111P | | 36 | | | | 1 | | 050-099, 162-199 |
| 401Y | 24 | | PY | QA | 0-0 | 23-42-11 | D06111P | | 38 | | | CAP | Y | | 050-099, 162-199 |
| 401Z | | | | QA | 0-0 | 23-42-11 | D06111P | | 40 | | | | 2 | | 050-099, 162-199 |
| A-A | | | | | 0-0 | 23-34-15 | D12230 | = CF | | | | | 1 | | 050-099, 162-199 |
| A-B | | | | | 0-0 | 23-34-15 | D12230 | F | | | | | 2 | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W3000

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|--------------|-----------------|----|-------|------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W3008 | 286T3008 | | | CREW REST TOP MODULE. | | | | | | | | | | | | | |
| 001 | 20 | PA | | 5-0 | 26-13-12 | D13964 | | 1 | | | | | D06123P | 30 | | | 050-099, 162-199 |
| 002 | 20 | PA | | 5-0 | 26-13-12 | D13964 | | 2 | | | | | D06123P | 25 | | | 050-099, 162-199 |
| 003 | 20 | PA | | 5-0 | 21-66-11 | D13964 | | 3 | | | | | D06123P | 5 | | | 050-099, 162-199 |
| 004 | 20 | PA | | 5-0 | 26-13-12 | D13964 | | 7 | | | | | D06123P | 27 | | | 050-099, 162-199 |
| 005 | 20 | PA | | 5-0 | 26-13-12 | D13964 | | 8 | | | | | D06123P | 26 | | | 050-099, 162-199 |
| 006 | 20 | PA | | 5-0 | 26-13-12 | D13964 | | 15 | | | | | D06123P | 29 | | | 050-099, 162-199 |
| 007 | 20 | PA | | 3-0 | 21-66-11 | SM00005 | | | | S | | | D02605 | 5 | | | 050-099, 162-199 |
| 008 | 20 | PA | | 6-0 | 21-66-11 | D06123P | | 19 | | | | | D02605 | 6 | | | 050-099, 162-199 |
| 009 | 20 | PA | | 6-0 | 21-66-11 | D06123P | | 18 | | | | | D02605 | 7 | | | 050-099, 162-199 |
| 010 | 20 | PA | | 6-0 | 21-66-11 | D06123P | | 17 | | | | | D02605 | 8 | | | 050-099, 162-199 |
| 011 | 20 | PA | | 6-0 | 21-66-11 | D06123P | | 16 | | | | | D02605 | 9 | | | 050-099, 162-199 |
| 012 | 20 | PA | | 6-0 | 21-66-11 | D06123P | | 15 | | | | | D02605 | 10 | | | 050-099, 162-199 |
| 013 | 20 | PA | | 3-0 | 21-66-11 | D02605 | | 11 | | | | | SM00005 | | S | | 050-099, 162-199 |
| 014 | 20 | PA | | 6-0 | 21-66-11 | D06123P | | 21 | | | | | D02605 | 12 | | | 050-099, 162-199 |
| 015 | 20 | PA | | 5-0 | 21-66-11 | D13964 | | 11 | | | | | D06123P | 3 | | | 050-099, 162-199 |
| 021 | 22 | PA | | 4-0 | 23-42-11 | B00420 | | | H/L | C | | | D06123P | 11 | | | 050-099, 162-199 |
| 022 | 20 | PA | | 4-0 | 23-42-11 | B00420 | | | GND | C | | | D06123P | 12 | | | 050-099, 162-199 |
| 023 | 22 | PA | | 4-0 | 23-42-11 | B00420 | | | 28V | C | | | D06123P | 13 | | | 050-099, 162-199 |
| 032 | 20 | PA | | 4-0 | 21-66-11 | SM00005 | | | | S | | | D06123P | 14 | | | 050-099, 162-199 |
| 201B | 22 | PB | IA | 90-0 | 21-66-11 | D06123P | | 22 | | | | | D02603 | 1 | | | 050-099, 162-199 |
| 201R | 22 | PB | IA | 0-0 | 21-66-11 | D06123P | | 23 | | | | | D02603 | 2 | | | 050-099, 162-199 |

WIRE LIST

D280T132

91-21-11

Section W3000

Page 4 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|-------|------|------|----------|-------------|----|---------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W3014 | 286T3014 | | | CTR MID MOD IND CLG.LTS ALTERNATE (STA 630-654+108) CATIA DESIGNED | | | | | | | | | | | | | |
| 001 | 20 | | PA | | 20-0 | 33-21-11 | D72056 | | | | 2 | | | STA0675R | CAP | Y | 280-299 |
| 002 | 20 | | PA | | 20-0 | 33-21-11 | D72056 | | | | 3 | | | STA0675R | CAP | Y | 280-299 |
| 003 | 20 | | PA | | 8-0 | 33-21-11 | D72056 | | | | 5 | | | D07100P | | 1 | 280-299 |
| 004 | 20 | | PA | | 8-0 | 33-21-11 | D72056 | | | | 7 | | | D07100P | | 2 | 280-299 |
| 005 | 20 | | PA | | 11-0 | 33-21-11 | SM00006 | | | | | 9 | | D07100P | | 3 | 280-299 |
| 006 | 20 | | PA | | 20-0 | 33-21-11 | D72056 | | | | 9 | | | STA0675L | CAP | Y | 280-299 |
| 007 | 20 | | PA | | 20-0 | 33-21-11 | D72056 | | | | 10 | | | STA0675L | CAP | Y | 280-299 |
| 008 | 20 | | PA | | 7-0 | 33-21-11 | D72056 | | | | 11 | | | SM00003 | | 9 | 280-299 |
| 009 | 20 | | PA | | 7-0 | 33-21-11 | D72056 | | | | 12 | | | SM00002 | | 9 | 280-299 |
| 010 | 20 | | PA | | 15-0 | 33-21-11 | SM00002 | | | | | 9 | | STA0675L | CAP | Y | 280-299 |
| 011 | 20 | | PA | | 15-0 | 33-21-11 | SM00003 | | | | | 9 | | STA0675R | CAP | Y | 280-299 |
| 012 | 20 | | PA | | 15-0 | 33-21-11 | SM00003 | | | | | 9 | | STA0675L | CAP | Y | 280-299 |
| 013 | 20 | | PA | | 15-0 | 33-21-11 | SM00002 | | | | | 9 | | STA0675R | CAP | Y | 280-299 |
| 014 | 20 | | PA | | 17-0 | 33-21-11 | D11166 | | | | 2 | | | STA0675R | CAP | Y | 280-299 |
| 015 | 20 | | PA | | 17-0 | 33-21-11 | D11166 | | | | 3 | | | ST0675R | CAP | Y | 280-299 |
| 016 | 20 | | PA | | 11-0 | 33-21-11 | D11166 | | | | 5 | | | D07100P | | 12 | 280-299 |
| 017 | 20 | | PA | | 11-0 | 33-21-11 | D11166 | | | | 7 | | | D07100P | | 4 | 280-299 |
| 018 | 20 | | PA | | 11-0 | 33-21-11 | SM00007 | | | | | 9 | | D07100P | | 5 | 280-299 |
| 019 | 20 | | PA | | 17-0 | 33-21-11 | D11166 | | | | 9 | | | STA0675L | CAP | Y | 280-299 |
| 020 | 20 | | PA | | 17-0 | 33-21-11 | D11166 | | | | 10 | | | STA0675L | CAP | Y | 280-299 |
| 021 | 20 | | PA | | 4-0 | 33-21-11 | D11166 | | | | 11 | | | SM00004 | | 9 | 280-299 |
| 022 | 20 | | PA | | 4-0 | 33-21-11 | D11166 | | | | 12 | | | SM00005 | | 9 | 280-299 |
| 023 | 20 | | PA | | 15-0 | 33-21-11 | SM00004 | | | | | 9 | | STA0675L | CAP | Y | 280-299 |
| 024 | 20 | | PA | | 15-0 | 33-21-11 | SM00005 | | | | | 9 | | STA0675R | CAP | Y | 280-299 |
| 025 | 20 | | PA | | 15-0 | 33-21-11 | SM00004 | | | | | 9 | | STA0675R | CAP | Y | 280-299 |
| 026 | 20 | | PA | | 15-0 | 33-21-11 | SM00005 | | | | | 9 | | STA0675L | CAP | Y | 280-299 |
| 027 | 20 | | PA | | 13-0 | 33-21-11 | D07098J | | | | 6 | | | D07100P | | 6 | 280-299 |
| 028 | 20 | | PA | | 13-0 | 33-21-11 | D07098J | | | | 7 | | | D07100P | | 7 | 280-299 |
| 029 | 20 | | PA | | 13-0 | 33-21-11 | D07098J | | | | 8 | | | D07100P | | 8 | 280-299 |
| 036 | 20 | | PA | | 6-0 | 33-21-11 | D72056 | | | | 8 | | | SM00006 | | 9 | 280-299 |
| 037 | 20 | | PA | | 15-0 | 33-21-11 | SM00006 | | | | | 9 | | STA0675L | CAP | Y | 280-299 |
| 038 | 20 | | PA | | 15-0 | 33-21-11 | SM00006 | | | | | 9 | | STA0675R | CAP | Y | 280-299 |
| 039 | 20 | | PA | | 4-0 | 33-21-11 | D11166 | | | | 8 | | | SM00007 | | 9 | 280-299 |
| 040 | 20 | | PA | | 15-0 | 33-21-11 | SM00007 | | | | | 9 | | STA0675R | CAP | Y | 280-299 |
| 041 | 20 | | PA | | 15-0 | 33-21-11 | SM00007 | | | | | 9 | | STA0675L | CAP | Y | 280-299 |
| W3016 | 286T3016 | | | CTR MID MOD IND CLG.LTS ALTERNATE (STA 654+109-763) CATIA DESIGNED | | | | | | | | | | | | | |
| 001 | 20 | | PA | | 11-0 | 33-21-11 | D72058 | | | | 2 | | | STA0680R | CAP | Y | 280-299 |
| 002 | 20 | | PA | | 11-0 | 33-21-11 | D72058 | | | | 3 | | | STA0680R | CAP | Y | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W3010
Page 1
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|----------|--------|-------------|--|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W3016 | 286T3016 | | | CTR MID MOD IND CLG.LTS ALTERNATE (STA 654+109-763) CATIA DESIGNED (continued) | | | | | | | | | | | | | | |
| 003 | 20 | | PA | 10-0 | 33-21-11 | D72058 | | 5 | | | | | D07098P | | 6 | | | 280-299 |
| 004 | 20 | | PA | 10-0 | 33-21-11 | D72058 | | 7 | | | | | D07098P | | 7 | | | 280-299 |
| 005 | 20 | | PA | 10-0 | 33-21-11 | SM00003 | | | 9 | | | | D07098P | | 8 | | | 280-299 |
| 006 | 20 | | PA | 9-0 | 33-21-11 | D72058 | | 9 | | | | | STA0680L | CAP | Y | | | 280-299 |
| 007 | 20 | | PA | 9-0 | 33-21-11 | D72058 | | 10 | | | | | STA0680L | CAP | Y | | | 280-299 |
| 008 | 20 | | PA | 2-0 | 33-21-11 | D72058 | | 11 | | | | | SM00001 | | 9 | | | 280-299 |
| 009 | 20 | | PA | 2-0 | 33-21-11 | D72058 | | 12 | | | | | SM00002 | | 9 | | | 280-299 |
| 010 | 20 | | PA | 9-0 | 33-21-11 | SM00001 | | | 9 | | | | STA0680L | CAP | Y | | | 280-299 |
| 011 | 20 | | PA | 9-0 | 33-21-11 | SM00002 | | | 9 | | | | STA0680L | CAP | Y | | | 280-299 |
| 012 | 20 | | PA | 11-0 | 33-21-11 | SM00002 | | | 9 | | | | STA0680R | CAP | Y | | | 280-299 |
| 013 | 20 | | PA | 11-0 | 33-21-11 | SM00001 | | | 9 | | | | STA0680R | CAP | Y | | | 280-299 |
| 014 | 20 | | PA | 9-0 | 33-21-11 | SM00003 | | | 9 | | | | STA0680L | CAP | Y | | | 280-299 |
| 015 | 20 | | PA | 11-0 | 33-21-11 | SM00003 | | | 9 | | | | STA0680R | CAP | Y | | | 280-299 |
| 016 | 20 | | PA | 2-0 | 33-21-11 | D72058 | | 8 | | | | | SM00003 | | 9 | | | 280-299 |

WIRE LIST
D280T132

91-21-11
Section W3010
Page 2 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3502 | 286T3502 | | | ENGINE-EEC/SCU/AUTOSTART | | | | | | | | | | | |
| 002 | 16 | HP | B | | 3-7 | 73-21-20 | D04224P | 13 | | | D08346P | 3 | | | ALL |
| 002Z | | | B | | 0-0 | 73-21-20 | D04224P | = CC | G3 | | D08346P | = CC | G3 | | ALL |
| 003 | 16 | HP | C | | 3-7 | 73-21-11 | D04224P | 4 | | | D08346P | 5 | | | ALL |
| 003Z | | | C | | 0-0 | 73-21-11 | D04224P | = CC | G3 | | D08346P | = CC | G3 | | ALL |
| 023 | 20 | HP | AW | | 3-7 | 73-21-11 | D04224P | 8 | | | D08346P | 7 | | | ALL |
| 023Z | | | AW | | 0-0 | 73-21-11 | D04224P | = CC | G3 | | D08346P | = CC | G3 | | ALL |
| 025 | 16 | HL | | | 1-4 | 73-21-11 | GD06589 | D.. | GW | | D08346P | 9 | | | ALL |
| 026 | 20 | HP | BA | | 3-7 | 78-36-11 | D04224P | 19 | | | D08346P | 8 | | | ALL |
| 026Z | | | BA | | 0-0 | 78-36-11 | D04224P | = CC | G3 | | D08346P | = CC | G3 | | ALL |
| 029 | 16 | HL | | | 1-4 | 73-21-20 | GD06589 | D.. | GW | | D08346P | 4 | | | ALL |
| 030 | 16 | HL | | | 1-4 | 73-21-11 | GD06589 | D.. | GW | | D08346P | 6 | | | ALL |
| 033 | 20 | HP | EB | | 4-0 | 73-21-14 | D11114 | M- | | | D04224P | 1 | | | 050-099, 155-199, 277-299 |
| 033 | 20 | HP | EB | | 5-0 | 73-21-14 | D11114 | M- | | | D04224P | 1 | | | 150-154, 275-276 |
| 033Z | | | EB | | 0-0 | 73-21-14 | D11114 | = CC | G3 | | D04224P | = CC | G3 | | ALL |
| 040 | 20 | HP | BO | | 4-0 | 73-21-11 | D04224P | 7 | | | D11114 | F | | | 050-099, 155-199, 277-299 |
| 040 | 20 | HP | BO | | 5-0 | 73-21-11 | D04224P | 7 | | | D11114 | F | | | 150-154, 275-276 |
| 040Z | | | BO | | 0-0 | 73-21-11 | D04224P | = CC | G3 | | D11114 | = CC | G3 | | ALL |
| 101 | 20 | HP | EA | | 4-0 | 73-21-14 | D04224P | 11 | | | D11114 | Q- | | | 050-099, 155-199, 277-299 |
| 101 | 20 | HP | EA | | 5-0 | 73-21-14 | D04224P | 11 | | | D11114 | Q- | | | 150-154, 275-276 |
| 101Z | | | EA | | 0-0 | 73-21-14 | D04224P | = CC | G3 | | D11114 | = CC | G3 | | ALL |
| 114 | 20 | HP | IN | | 4-0 | 73-21-19 | D04224P | 18 | | | D11114 | J | | | 050-099, 155-199, 277-299 |
| 114 | 20 | HP | IN | | 5-0 | 73-21-19 | D04224P | 18 | | | D11114 | J | | | 150-154, 275-276 |
| 114Z | | | IN | | 0-0 | 73-21-19 | D04224P | = CC | G3 | | D11114 | = CC | G3 | | ALL |
| 200B | 20 | HQ | IP | | 4-0 | 73-21-14 | D04224P | 10 | | | D11114 | H- | | | 050-099, 155-199, 277-299 |
| 200B | 20 | HQ | IP | | 5-0 | 73-21-14 | D04224P | 10 | | | D11114 | H- | | | 150-154, 275-276 |
| 200R | 20 | HQ | IP | | 0-0 | 73-21-14 | D04224P | 9 | | | D11114 | T | | | ALL |
| 200Z | | | IP | | 0-0 | 73-21-14 | D04224P | = CC | G3 | | D11114 | = CC | G3 | | ALL |
| 201B | 20 | HQ | R | | 3-7 | 77-12-12 | D04224P | 3 | | | D08346P | 11 | | | ALL |
| 201R | 20 | HQ | R | | 0-0 | 77-12-12 | D04224P | 2 | | | D08346P | 10 | | | ALL |
| 201Z | | | R | | 0-0 | 77-12-12 | D04224P | = CC | G3 | | D08346P | = CC | G3 | | ALL |
| 203B | 20 | HQ | U | | 4-0 | 73-21-13 | D04224P | 15 | | | D11114 | Y | | | 050-099, 155-199, 277-299 |
| 203B | 20 | HQ | U | | 5-0 | 73-21-13 | D04224P | 15 | | | D11114 | Y | | | 150-154, 275-276 |
| 203R | 20 | HQ | U | | 0-0 | 73-21-13 | D04224P | 16 | | | D11114 | C | | | ALL |

WIRE LIST
D280T132

91-21-11
Section W3500
Page 1
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|------------------------------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3502 | 286T3502 | | | ENGINE-EEC/SCU/AUTOSTART (continued) | | | | | | | | | | | | |
| 203Z | | | U | 0-0 | 73-21-13 | D04224P | =CC | G3 | | D11114 | =CC | G3 | | ALL | | |
| 204B | 20 | HQ | V | 4-0 | 73-21-14 | D04224P | | 24 | | D11114 | P | | | 050-099, 155-199, 277-299 | | |
| 204B | 20 | HQ | V | 5-0 | 73-21-14 | D04224P | | 24 | | D11114 | P | | | 150-154, 275-276 | | |
| 204R | 20 | HQ | V | 0-0 | 73-21-14 | D04224P | | 23 | | D11114 | R | | | ALL | | |
| 204Z | | | V | 0-0 | 73-21-14 | D04224P | =CC | G3 | | D11114 | =CC | G3 | | ALL | | |
| 205B | 20 | HQ | W | 4-0 | 73-21-14 | D04224P | | 6 | | D11114 | J- | | | 050-099, 155-199, 277-299 | | |
| 205B | 20 | HQ | W | 5-0 | 73-21-14 | D04224P | | 6 | | D11114 | J- | | | 150-154, 275-276 | | |
| 205R | 20 | HQ | W | 0-0 | 73-21-14 | D04224P | | 5 | | D11114 | V | | | ALL | | |
| 205Z | | | W | 0-0 | 73-21-14 | D04224P | =CC | G3 | | D11114 | =CC | G3 | | ALL | | |
| 206B | 20 | HQ | IF | 1-9 | 73-21-11 | D08370P | | 16 | | SM00002 | | 8 | | ALL | | |
| 206R | 20 | HQ | IF | 0-0 | 73-21-11 | D08370P | | 15 | | SM00001 | | 8 | | ALL | | |
| 206Z | | | IF | 0-0 | 73-21-11 | D08370P | =CC | G3 | | SM00001 | REF | V | | ALL | | |
| 212B | 20 | HQ | IL | 4-0 | 73-21-14 | D04224P | | 33 | | D11114 | I- | | | 050-099, 155-199, 277-299 | | |
| 212B | 20 | HQ | IL | 5-0 | 73-21-14 | D04224P | | 33 | | D11114 | I- | | | 150-154, 275-276 | | |
| 212R | 20 | HQ | IL | 0-0 | 73-21-14 | D04224P | | 32 | | D11114 | U | | | ALL | | |
| 212Z | | | IL | 0-0 | 73-21-14 | D04224P | =CC | G3 | | D11114 | =CC | G3 | | ALL | | |
| 213B | 20 | HQ | IM | 4-0 | 73-21-17 | D04224P | | 42 | | D11114 | S- | | | 050-099, 155-199, 277-299 | | |
| 213B | 20 | HQ | IM | 5-0 | 73-21-17 | D04224P | | 42 | | D11114 | S- | | | 150-154, 275-276 | | |
| 213R | 20 | HQ | IM | 0-0 | 73-21-17 | D04224P | | 41 | | D11114 | H | | | ALL | | |
| 213Z | | | IM | 0-0 | 73-21-17 | D04224P | =CC | G3 | | D11114 | =CC | G3 | | ALL | | |
| 222B | 20 | HQ | MG | 4-0 | 73-21-17 | D04224P | | 28 | | D11114 | C- | | | 050-099, 155-199, 277-299 | | |
| 222B | 20 | HQ | MG | 5-0 | 73-21-17 | D04224P | | 28 | | D11114 | C- | | | 150-154, 275-276 | | |
| 222R | 20 | HQ | MG | 0-0 | 73-21-12 | D04224P | | 17 | | D11114 | K- | | | ALL | | |
| 222Z | | | MG | 0-0 | 73-21-12 | D04224P | =CC | G3 | | D11114 | =CC | G3 | | ALL | | |
| 225B | 20 | HQ | IY | 2-0 | 73-21-11 | D11114 | | S | | SM00002 | | 8 | | ALL | | |
| 225R | 20 | HQ | IY | 0-0 | 73-21-11 | D11114 | | P- | | SM00001 | | 8 | | ALL | | |
| 225Z | | | IY | 0-0 | 73-21-11 | D11114 | =CC | G3 | | SM00001 | REF | V | | ALL | | |
| 227B | 20 | HQ | JB | 1-11 | 73-21-11 | D15802P | | 2 | | SM00002 | | 8 | | ALL | | |
| 227R | 20 | HQ | JB | 0-0 | 73-21-11 | D15802P | | 1 | | SM00001 | | 8 | | ALL | | |
| 227Z | | | JB | 0-0 | 73-21-11 | D15802P | =CC | G7 | | SM00001 | REF | V | | ALL | | |
| 231B | 20 | HQ | JF | 3-7 | 78-36-11 | D04224P | | 34 | | D08346P | | 15 | | ALL | | |
| 231R | 20 | HQ | JF | 0-0 | 78-36-11 | D04224P | | 31 | | D08346P | | 14 | | ALL | | |
| 231Z | | | JF | 0-0 | 78-36-11 | D04224P | =CC | G3 | | D08346P | =CC | G3 | | ALL | | |
| 233B | 20 | HQ | JH | 3-7 | 78-36-11 | D04224P | | 30 | | D08346P | | 16 | | ALL | | |

WIRE LIST

D280T132

91-21-11

Section W3500

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3502 | 286T3502 | | | ENGINE-EEC/SCU/AUTOSTART (continued) | | | | | | | | | | | | |
| 233R | 20 | HQ | JH | 0-0 | 78-36-11 | D04224P | 29 | | | | D08346P | 17 | | | ALL | |
| 233Z | | | JH | 0-0 | 78-36-11 | D04224P | =CC | G3 | | | D08346P | =CC | G3 | | ALL | |
| 301B | 20 | HR | S | 4-0 | 73-21-13 | D04224P | 27 | | | | D11114 | X | | | 050-099, 155-199, 277-299 | |
| 301B | 20 | HR | S | 5-0 | 73-21-13 | D04224P | 27 | | | | D11114 | X | | | 150-154, 275-276 | |
| 301R | 20 | HR | S | 0-0 | 73-21-13 | D04224P | 26 | | | | D11114 | A | | | ALL | |
| 301Y | 20 | HR | S | 0-0 | 73-21-13 | D04224P | 25 | | | | D11114 | B | | | ALL | |
| 301Z | | | S | 0-0 | 73-21-13 | D04224P | =CC | G3 | | | D11114 | =CC | G3 | | ALL | |
| 305B | 20 | HR | ME | 3-7 | 73-21-11 | D04224P | 40 | | | | D08346P | 2 | | | ALL | |
| 305R | 20 | HR | ME | 0-0 | 73-21-11 | D04224P | 39 | | | | D08346P | 1 | | | ALL | |
| 305Y | 20 | HR | ME | 0-0 | 73-21-11 | D04224P | 38 | | | | D08346P | 12 | | | ALL | |
| 305Z | | | ME | 0-0 | 73-21-11 | D04224P | =CC | G3 | | | D08346P | =CC | G3 | | ALL | |
| 401B | 20 | HS | MC | 4-0 | 73-21-14 | D04224P | 12 | | | | D11114 | D | | | 050-099, 155-199, 277-299 | |
| 401B | 20 | HS | MC | 5-0 | 73-21-14 | D04224P | 12 | | | | D11114 | D | | | 150-154, 275-276 | |
| 401G | 20 | HS | MC | 0-0 | 73-21-14 | D04224P | 22 | | | | D11114 | G | | | ALL | |
| 401R | 20 | HS | MC | 0-0 | 73-21-14 | D04224P | 20 | | | | D11114 | R- | | | ALL | |
| 401Y | 20 | HS | MC | 0-0 | 73-21-14 | D04224P | 21 | | | | D11114 | G- | | | ALL | |
| 401Z | | | MC | 0-0 | 73-21-14 | D04224P | =CC | G3 | | | D11114 | =CC | G3 | | ALL | |
| W3504 | 286T3504 | | | ENGINE-EEC/AVM/AUTOSTART | | | | | | | | | | | | |
| 001 | 16 | HP | A | 3-8 | 30-34-11 | D08320P | 1 | | | | D08316P | 1 | | | ALL | |
| 001Z | | | A | 0-0 | 30-34-11 | D08320P | =CC | G3 | | | D08316P | =CC | G3 | | ALL | |
| 002 | 16 | HP | B | 4-1 | 73-21-20 | D08320P | 13 | | | | D08330P | 3 | | | ALL | |
| 002Z | | | B | 0-0 | 73-21-20 | D08320P | =CC | G3 | | | D08330P | =CC | G3 | | ALL | |
| 003 | 16 | HP | C | 4-1 | 73-21-11 | D08320P | 4 | | | | D08330P | 5 | | | ALL | |
| 003Z | | | C | 0-0 | 73-21-11 | D08320P | =CC | G3 | | | D08330P | =CC | G3 | | ALL | |
| 004 | 16 | HL | | 3-6 | 30-34-11 | GD06701 | A.. | GW | | | D08316P | 2 | | | ALL | |
| 005 | 16 | HL | | 3-10 | 73-21-11 | D08330P | 6 | | | | GD06593 | D.. | GW | | 050-099, 155-199, 277-299 | |
| 01TI | | | IR | 0-0 | 77-31-11 | D10994 | DED | | | | D08336P | 3 | | | 050-099, 155-199, 277-299 | |
| 01TO | | | IR | 0-0 | 77-31-11 | D10994 | =CC | K | | | D08336P | =CC | G3 | | 050-099, 155-199, 277-299 | |
| 01TR | 20 | RQ | IR | 5-1 | 77-31-11 | D10994 | 1 | | | | D08336P | 2 | | | 050-099, 155-199, 277-299 | |
| 01TW | 20 | RQ | IR | 0-0 | 77-31-11 | D10994 | 2 | | | | D08336P | 1 | | | 050-099, 155-199, 277-299 | |
| 024 | 16 | HL | | 3-10 | 73-21-11 | GD06593 | D.. | GW | | | D08330P | 9 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W3500

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3504 | 286T3504 | | | ENGINE-EEC/AVM/AUTOSTART (continued) | | | | | | | | | | | | |
| 026 | 20 | HP | BA | 4-1 | 78-36-11 | D08320P | 19 | | | | D08330P | 8 | | | ALL | |
| 026Z | | | BA | 0-0 | 78-36-11 | D08320P | = CC | G3 | | | D08330P | = CC | G3 | | ALL | |
| 027 | 20 | HP | BB | 4-1 | 73-21-11 | D08320P | 8 | | | | D08330P | 7 | | | ALL | |
| 027Z | | | BB | 0-0 | 73-21-11 | D08320P | = CC | G3 | | | D08330P | = CC | G3 | | ALL | |
| 028 | 20 | HP | EB | 3-10 | 73-21-14 | D11686 | M- | | | | D08320P | 14 | | | ALL | |
| 028Z | | | EB | 0-0 | 73-21-14 | D11686 | = CC | G3 | | | D08320P | = CC | G3 | | ALL | |
| 029 | 16 | HL | | 3-10 | 73-21-20 | GD06593 | D.. | GW | | | D08330P | 4 | | | ALL | |
| 030 | 16 | HL | | 3-10 | 73-21-11 | GD06593 | D.. | GW | | | D08330P | 6 | | | 150-154, 275-276 | |
| 033 | 16 | HL | | 1-5 | 73-21-13 | D08336P | 4 | | | | GD06635 | S.. | GW | | 050-099, 155-199, 277-299 | |
| 033 | 16 | HL | BH | 1-5 | 73-31-11 | D08336P | 4 | | | | GD06635 | S.. | GW | | 150-154, 275-276 | |
| 034 | 16 | HL | | 1-5 | 73-21-13 | D08336P | 5 | | | | GD06635 | S.. | GW | | 050-099, 155-199, 277-299 | |
| 034 | 16 | HL | BI | 1-5 | 73-31-11 | D08336P | 5 | | | | GD06635 | S.. | GW | | 150-154, 275-276 | |
| 040 | 20 | HP | BO | 3-10 | 73-21-11 | D08320P | 7 | | | | D11686 | F | | | ALL | |
| 040Z | | | BO | 0-0 | 73-21-11 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| 101 | 20 | HP | EA | 3-10 | 73-21-14 | D08320P | 9 | | | | D11686 | Q- | | | ALL | |
| 101Z | | | EA | 0-0 | 73-21-14 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| 114 | 20 | HP | IN | 3-10 | 73-21-19 | D08320P | 18 | | | | D11686 | J | | | ALL | |
| 114Z | | | IN | 0-0 | 73-21-19 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| 201B | 20 | HQ | R | 3-10 | 77-12-11 | D08320P | 3 | | | | D11686 | E | | | ALL | |
| 201R | 20 | HQ | R | 0-0 | 77-12-11 | D08320P | 2 | | | | D11686 | A- | | | ALL | |
| 201Z | | | R | 0-0 | 77-12-11 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| 203B | 20 | HQ | U | 3-10 | 73-21-13 | D08320P | 15 | | | | D11686 | Y | | | ALL | |
| 203R | 20 | HQ | U | 0-0 | 73-21-13 | D08320P | 16 | | | | D11686 | C | | | ALL | |
| 203Z | | | U | 0-0 | 73-21-13 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| 205B | 20 | HQ | W | 3-10 | 73-21-14 | D08320P | 6 | | | | D11686 | J- | | | ALL | |
| 205R | 20 | HQ | W | 0-0 | 73-21-14 | D08320P | 5 | | | | D11686 | V | | | ALL | |
| 205Z | | | W | 0-0 | 73-21-14 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| 206B | 20 | HQ | IF | 3-11 | 73-21-11 | D11686 | S | | | | D15802J | 2 | | | ALL | |
| 206R | 20 | HQ | IF | 0-0 | 73-21-11 | D11686 | P- | | | | D15802J | 1 | | | ALL | |
| 206Z | | | IF | 0-0 | 73-21-11 | D11686 | = CC | G3 | | | D15802J | = CC | G7 | | ALL | |
| 207B | 20 | HQ | IG | 3-10 | 73-21-14 | D08320P | 24 | | | | D11686 | P | | | ALL | |
| 207R | 20 | HQ | IG | 0-0 | 73-21-14 | D08320P | 23 | | | | D11686 | R | | | ALL | |
| 207Z | | | IG | 0-0 | 73-21-14 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| 208B | 20 | HQ | IH | 3-10 | 73-21-14 | D08320P | 37 | | | | D11686 | H- | | | ALL | |
| 208R | 20 | HQ | IH | 0-0 | 73-21-14 | D08320P | 36 | | | | D11686 | T | | | ALL | |
| 208Z | | | IH | 0-0 | 73-21-14 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| 209B | 20 | HQ | ME | 4-1 | 73-21-11 | D08320P | 40 | | | | D08330P | 2 | | | ALL | |

WIRE LIST

D280T132

91-21-11

Section W3500

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3504 | 286T3504 | | | ENGINE-EEC/AVM/AUTOSTART (continued) | | | | | | | | | | | | |
| 209R | 20 | HQ | ME | 0-0 | 73-21-11 | D08320P | 39 | | | | D08330P | 1 | | | ALL | |
| 209Z | | | ME | 0-0 | 73-21-11 | D08320P | = CC | G3 | | | D08330P | = CC | G3 | | ALL | |
| 211B | 20 | HQ | MG | 3-10 | 73-21-17 | D08320P | 28 | | | | D11686 | C- | | | ALL | |
| 211R | 20 | HQ | MG | 0-0 | 73-21-12 | D08320P | 17 | | | | D11686 | K- | | | ALL | |
| 211Z | | | MG | 0-0 | 73-21-12 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| 212B | 20 | HQ | IL | 3-10 | 73-21-14 | D08320P | 33 | | | | D11686 | I- | | | ALL | |
| 212R | 20 | HQ | IL | 0-0 | 73-21-14 | D08320P | 32 | | | | D11686 | U | | | ALL | |
| 212Z | | | IL | 0-0 | 73-21-14 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| 213B | 20 | HQ | IM | 3-10 | 73-21-17 | D08320P | 42 | | | | D11686 | S- | | | ALL | |
| 213R | 20 | HQ | IM | 0-0 | 73-21-17 | D08320P | 41 | | | | D11686 | H | | | ALL | |
| 213Z | | | IM | 0-0 | 73-21-17 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| 216B | 20 | HQ | D | 4-1 | 31-35-14 | D08320P | 11 | | | | D08330P | 11 | | | ALL | |
| 216R | 20 | HQ | D | 0-0 | 31-35-14 | D08320P | 10 | | | | D08330P | 10 | | | ALL | |
| 216Z | | | D | 0-0 | 31-35-14 | D08320P | = CC | G3 | | | D08330P | = CC | G3 | | ALL | |
| 217B | 20 | HQ | E | 7-1 | SPARE | D08336P | 9 | | | | D08330P | 13 | | | ALL | |
| 217R | 20 | HQ | E | 0-0 | SPARE | D08336P | 8 | | | | D08330P | 12 | | | ALL | |
| 217Z | | | E | 0-0 | SPARE | D08336P | = CC | GW | | | D08330P | = CC | G3 | | ALL | |
| 218R | 20 | RJ | IR | 5-1 | 77-31-11 | D08336P | 2 | | | | D10994 | 1 | | | 150-154, 275-276 | |
| 218W | 20 | RJ | IR | 0-0 | 77-31-11 | D08336P | 1 | | | | D10994 | 2 | | | 150-154, 275-276 | |
| 218Z | | | IR | 0-0 | 77-31-11 | D08336P | 3 | | | | D10994 | DED | | | 150-154, 275-276 | |
| 231B | 20 | HQ | BF | 4-1 | 78-36-11 | D08320P | 34 | | | | D08330P | 15 | | | ALL | |
| 231R | 20 | HQ | BF | 0-0 | 78-36-11 | D08320P | 31 | | | | D08330P | 14 | | | ALL | |
| 231Z | | | BF | 0-0 | 78-36-11 | D08320P | = CC | G3 | | | D08330P | = CC | G3 | | ALL | |
| 233B | 20 | HQ | BG | 4-1 | 78-36-11 | D08320P | 30 | | | | D08330P | 16 | | | ALL | |
| 233R | 20 | HQ | BG | 0-0 | 78-36-11 | D08320P | 29 | | | | D08330P | 17 | | | ALL | |
| 233Z | | | BG | 0-0 | 78-36-11 | D08320P | = CC | G3 | | | D08330P | = CC | G3 | | ALL | |
| 301B | 20 | HR | S | 3-10 | 73-21-13 | D08320P | 27 | | | | D11686 | X | | | ALL | |
| 301R | 20 | HR | S | 0-0 | 73-21-13 | D08320P | 26 | | | | D11686 | A | | | ALL | |
| 301Y | 20 | HR | S | 0-0 | 73-21-13 | D08320P | 25 | | | | D11686 | B | | | ALL | |
| 301Z | | | S | 0-0 | 73-21-13 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| 401B | 20 | HS | MC | 3-10 | 73-21-14 | D08320P | 12 | | | | D11686 | D | | | ALL | |
| 401G | 20 | HS | MC | 0-0 | 73-21-14 | D08320P | 22 | | | | D11686 | G | | | ALL | |
| 401R | 20 | HS | MC | 0-0 | 73-21-14 | D08320P | 20 | | | | D11686 | R- | | | ALL | |
| 401Y | 20 | HS | MC | 0-0 | 73-21-14 | D08320P | 21 | | | | D11686 | G- | | | ALL | |
| 401Z | | | MC | 0-0 | 73-21-14 | D08320P | = CC | G3 | | | D11686 | = CC | G3 | | ALL | |
| W3506 | 286T3506 | | | ENGINE-S2A-ENG INSTR & FIRE DET | | | | | | | | | | | | |
| 006 | 18 | HL | | 11-2 | 80-11-11 | D04230P | 4 | | | | D10970 | 3 | | | ALL | |
| 007 | 18 | HL | | 11-2 | 80-11-11 | D04230P | 5 | | | | D10970 | 6 | | | ALL | |

WIRE LIST
D280T132

91-21-11
Section W3500
Page 5
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|---------------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3506 | 286T3506 | | | ENGINE-S2A-ENG INSTR & FIRE DET (continued) | | | | | | | | | | | |
| 008 | 18 | | HL | 11-2 | 80-11-11 | D04230P | | 6 | | | D10970 | | 1 | | ALL |
| 009 | 18 | | HL | 9-11 | 80-11-11 | GD06597 | | D.. | GW | | D10970 | | 2 | | ALL |
| 010 | 18 | | HL | 9-11 | 80-11-11 | GD06597 | | D.. | GW | | D10970 | | 4 | | ALL |
| 011 | 18 | | HL | 9-11 | 80-11-11 | GD06597 | | D.. | GW | | D10970 | | 5 | | ALL |
| 012 | 18 | | HL | 9-10 | 80-11-11 | GD06659 | | S.. | GW | | D10970 | | 7 | | ALL |
| 451R | 16 | | 9P | 4-11 | 26-11-12 | D04230P | | 14 | | | TS0684 | A/1 | GW | | ALL |
| 452R | 16 | | 9P | 6-7 | 26-11-11 | D04230P | | 15 | | | TS0681 | A/1 | G3 | | ALL |
| 453R | 16 | | 9P | 11-0 | 76-11-11 | D04230P | | 10 | | | SM00001 | | 8 | | ALL |
| 454R | 16 | | 9P | 2-0 | 76-11-11 | SM00001 | | | 8 | | D08312 | | 6 | | 050, 155 |
| 454R | 16 | | 9P | 0-9 | 76-11-11 | SM00001 | | | 8 | | D08312 | | 6 | | 051-099, 150-154, 156-199, 275-299 |
| 455R | 16 | | 9P | 10-1 | 76-11-11 | GD06595 | | D.. | GW | | D08312 | | 4 | | ALL |
| 456R | 16 | | 9P | 10-1 | 76-11-11 | GD06595 | | D.. | GW | | D08312 | | 8 | | ALL |
| 457R | 16 | | 9P | 10-1 | 76-11-11 | GD06595 | | D.. | GW | | D08312 | | 10 | | ALL |
| 458R | 16 | | 9P | 10-1 | 76-11-11 | GD06595 | | D.. | GW | | D08312 | | 14 | | ALL |
| 460 | 18 | | HL | 11-3 | 76-11-11 | D04230P | | 8 | | | D08312 | | 3 | | ALL |
| 461R | 16 | | 9P | 11-3 | 76-11-11 | D04230P | | 9 | | | D08312 | | 13 | | ALL |
| 462R | 16 | | 9P | 11-3 | 76-11-11 | D04230P | | 12 | | | D08312 | | 9 | | ALL |
| 463R | 16 | | 9P | 9-10 | 76-11-11 | GD06659 | | S.. | GW | | D08312 | | 5 | | ALL |
| 472R | 16 | | 9P | 2-0 | 76-11-11 | SM00001 | | | 8 | | D08312 | | 1 | | 050, 155 |
| 472R | 16 | | 9P | 0-9 | 76-11-11 | SM00001 | | | 8 | | D08312 | | 1 | | 051-099, 150-154, 156-199, 275-299 |
| W3508 | 286T3508 | | | ENGINE-ENG INSTR | | | | | | | | | | | |
| 003 | 18 | | HL | 8-0 | 73-34-11 | GD06587 | | D.. | GW | | D10996 | | C | | ALL |
| 004 | 18 | | HL | 8-0 | 73-34-11 | GD06621 | | S.. | GW | | D10996 | | B | | ALL |
| 005 | 18 | | HL | 11-0 | 73-34-11 | D04232P | | 2 | | | D10996 | | A | | ALL |
| 006 | 18 | | HL | 13-0 | 36-11-61 | GD06621 | | S.. | GW | | D11116 | | 4 | | ALL |
| 007 | 18 | | HL | 12-0 | 36-11-61 | D04232P | | 3 | | | D11116 | | 1 | | ALL |
| 008 | 18 | | HL | 12-0 | 36-11-61 | D04232P | | 4 | | | D11116 | | 2 | | ALL |
| 009 | 18 | | HL | 12-0 | 36-11-61 | D04232P | | 5 | | | D11116 | | 3 | | ALL |
| 017 | 18 | | HL | 13-0 | 29-11-11 | D04232P | | 9 | | | D10980 | | 3 | | ALL |
| 018 | 18 | | HL | 10-0 | 29-11-11 | GD06587 | | D.. | GW | | D10980 | | 1 | | ALL |
| 019 | 18 | | HL | 10-0 | 29-11-11 | GD06621 | | S.. | GW | | D10980 | | 2 | | ALL |
| 021 | 18 | | HL | 12-0 | 74-31-21 | D04232P | | 12 | | | D10976 | | B | | ALL |
| 022 | 18 | | HL | 9-0 | 74-31-21 | GD06613 | | A.. | GW | | D10976 | | A | | ALL |
| 030 | 18 | | HL | 5-0 | 79-32-11 | D10982 | | 4 | DK | | GD06633 | S.. | GW | | ALL |
| 031 | 18 | | HL | 7-0 | 79-32-11 | D04232P | | 16 | | | D10982 | | 2 | DK | ALL |
| 032 | 18 | | HL | 7-0 | 79-32-11 | D04232P | | 17 | | | D10982 | | 3 | DK | ALL |

WIRE LIST

D280T132

91-21-11

Section W3500

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3508 | 286T3508 | | | ENGINE-ENG INSTR (continued) | | | | | | | | | | | |
| 033 | 18 | | HL | | 7-0 | 79-32-11 | D04232P | | 18 | | D10982 | 1 | DK | | ALL |
| 034 | 18 | | HL | | 5-0 | 36-11-61 | D04232P | | 19 | | V00352 | 1 | GW | * | ALL |
| 035 | 18 | | HL | | 5-0 | 36-11-61 | D04232P | | 20 | | V00352 | 2 | GW | | ALL |
| 036 | 18 | | HL | | 5-0 | 36-11-61 | D04232P | | 21 | | V00352 | 3 | GW | * | ALL |
| 037 | 18 | | HL | | 5-0 | 36-11-61 | D04232P | | 22 | | V00352 | 3 | GW | * | ALL |
| 038 | 16 | | HL | | 4-0 | 73-21-13 | D04232P | | 37 | | GD06659 | S.. | GW | | ALL |
| 039 | 16 | | HL | | 4-0 | 73-21-13 | D04232P | | 38 | | GD06659 | S.. | GW | | ALL |
| 040 | 18 | | HL | | 5-0 | 36-11-61 | D04232P | | 23 | | V00352 | 1 | GW | * | ALL |

WIRE LIST
D280T132

91-21-11
Section W3500
Page 7 End
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|-------------------------|----------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|---|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W3510 | 286T3510 | | | ENGINE-ENG INSTR | | | | | | | | | | | | | |
| 001 | 18 | | HL | | 11-0 36-11-61 | D04208P | | 1 | | | | | D10984 | 1 | | | ALL |
| 002 | 18 | | HL | | 11-0 36-11-61 | D04208P | | 2 | | | | | D10984 | 3 | | | ALL |
| 003 | 18 | | HL | | 11-0 36-11-61 | D04208P | | 3 | | | | | D10984 | 7 | | | ALL |
| 004 | 18 | | HL | | 11-0 36-11-61 | D04208P | | 4 | | | | | D10984 | 8 | | | ALL |
| 005 | 18 | | HL | | 11-0 36-11-61 | D04208P | | 5 | | | | | D10984 | 9 | | | ALL |
| 006 | 18 | | HL | | 11-0 36-11-61 | D04208P | | 6 | | | | | D10984 | 5 | | | ALL |
| 007 | 18 | | HL | | 11-0 36-11-61 | D04208P | | 7 | | | | | D10984 | 10 | | | ALL |
| 008 | 18 | | HL | | 12-5 36-11-61 | GD06627 | | S.. | GW | | | | D10984 | 12 | | | ALL |
| 009 | 18 | | HL | | 2-0 36-11-61 | SM00001 | | | 8 | | | | D10984 | 2 | | | ALL |
| 010 | 18 | | HL | | 2-0 36-11-61 | SM00001 | | | 8 | | | | D10984 | 4 | | | ALL |
| 011 | 18 | | HL | | 2-0 36-11-61 | SM00001 | | | 8 | | | | D10984 | 6 | | | ALL |
| 012 | 18 | | HL | | 2-0 36-11-61 | SM00001 | | | 8 | | | | D10984 | 11 | | | ALL |
| 014 | 18 | | HL | | 11-0 36-11-61 | D04208P | | | 9 | | | | SM00001 | | 8 | | ALL |
| 015 | 18 | | HL | | 12-0 36-11-61 | SM00001 | | | 8 | | | | SM00002 | | 8 | | ALL |
| 016 | 18 | | HL | | 12-0 36-11-61 | V00347 | | | 2 | GW | | | SM00002 | | 8 | | ALL |
| 017 | 18 | | HL | | 5-0 36-11-61 | D04208P | | | 10 | | | | V00347 | 1 | GW | * | ALL |
| 018 | 18 | | HL | | 5-0 36-11-61 | D04208P | | | 11 | | | | V00347 | 3 | GW | * | ALL |
| 019 | 18 | | HL | | 8-10 79-31-11 | D04208P | | | 12 | | | | D10992 | 1 | | | ALL |
| 020 | 18 | | HL | | 8-10 79-31-11 | D04208P | | | 13 | | | | D10992 | 2 | | | ALL |
| 021 | 18 | | HL | | 8-10 79-31-11 | D04208P | | | 14 | | | | D10992 | 3 | | | ALL |
| 022 | 18 | | HL | | 10-11 74-31-11 | D04208P | | | 15 | | | | D10978 | B | | | ALL |
| 023 | 18 | | HL | | 8-6 74-31-11 | GD06615 | | A.. | GW | | | | D10978 | A | | | ALL |
| 024 | 18 | | HL | | 8-11 79-35-11 | GD06591 | | D.. | GW | | | | D10974 | 2 | | | ALL |
| 025 | 18 | | HL | | 8-9 79-35-11 | GD06617 | | S.. | GW | | | | D10974 | 4 | | | ALL |
| 026 | 18 | | HL | | 10-6 79-35-11 | D04208P | | | 16 | | | | D10974 | 3 | | | ALL |
| 027 | 18 | | HL | | 6-3 79-33-11 | D04208P | | | 22 | | | | D10988 | 1 | | | ALL |
| 028 | 18 | | HL | | 6-1 79-33-11 | GD06591 | | D.. | GW | | | | D10988 | 2 | | | ALL |
| 029 | 18 | | HL | | 5-2 79-33-11 | GD06633 | | S.. | GW | | | | D10988 | 4 | | | ALL |
| 030 | 18 | | HL | | 12-3 73-33-11 | D10998 | | | 1 | DK | | | D04208P | 25 | | | ALL |
| 031 | 18 | | HL | | 12-3 73-33-11 | D10998 | | | 2 | DK | | | D04208P | 23 | | | ALL |
| 032 | 18 | | HL | | 12-3 73-33-11 | D10998 | | | 3 | DK | | | D04208P | 24 | | | ALL |
| 033 | 18 | | HL | | 11-11 73-33-11 | D10998 | | | 4 | DK | | | GD06629 | S.. | GW | | ALL |
| 034 | 20 | | HP | S | 6-8 73-31-11 | GD06627 | | S.. | GW | | | | D11000 | 4 | | | ALL |
| 034Z | | | | S | 0-0 73-31-11 | GD06627 | | DED | | | | | D11000 | DED | | | ALL |
| 041 | 18 | | HL | | 6-10 79-31-11 | D10992 | | | 4 | | | | GD06633 | S.. | GW | | ALL |
| 042 | 16 | | HL | | 3-5 73-21-13 | D04208P | | | 8 | | | | GD06629 | S.. | GW | | ALL |
| 043 | 16 | | HL | | 3-8 73-21-13 | D04208P | | | 20 | | | | GD06617 | S.. | GW | | ALL |
| 044 | 18 | | HL | | 5-0 36-11-61 | D04208P | | | 29 | | | | V00347 | 3 | GW | * | ALL |
| 045 | 18 | | HL | | 5-0 36-11-61 | D04208P | | | 30 | | | | V00347 | 1 | GW | * | ALL |

WIRE LIST

D280T132

91-21-11

Section W3510

Page 1

Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|--------|------|------|--------|---|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3510 | 286T3510 | | | ENGINE-ENG INSTR (continued) | | | | | | | | | | | |
| 302B | 20 | HR | T | | 9-1 | 73-31-11 | D04208P | | 18 | | D11000 | | 2 | | ALL |
| 302R | 20 | HR | T | | 0-0 | 73-31-11 | D04208P | | 17 | | D11000 | | 1 | | ALL |
| 302Y | 20 | HR | T | | 0-0 | 73-31-11 | D04208P | | 19 | | D11000 | | 3 | | ALL |
| 302Z | | | T | | 0-0 | 73-31-11 | D04208P | = CC | M | | D11000 | DED | | | 050-099, 150-155, 162-165, 275-276 156-157, 166-199, 277-299 |
| 302Z | | | T | | 0-0 | 73-31-11 | D04208P | = CC | G3 | | D11000 | DED | | | |
| W3512 | 286T3512 | | | ENGINE-S2 FIRE DETECTION | | | | | | | | | | | |
| 451R | 16 | 9P | | | 3-4 | 26-11-11 | TS0681 | A/1 | GW | | TS0682 | A/1 | GW | | ALL |
| 452R | 16 | 9P | | | 3-4 | 26-11-11 | TS0681 | B/2 | G3 | | TS0682 | B/2 | G3 | | ALL |
| W3514 | 286T3514 | | | ENGINE-S2 FIRE DETECTION | | | | | | | | | | | |
| 451R | 16 | 9P | | | 9-11 | 26-11-11 | TS0683 | A/1 | GW | | TS0682 | A/1 | G3 | | ALL |
| 452R | 16 | 9P | | | 9-11 | 26-11-11 | TS0683 | B/2 | G3 | | TS0682 | B/2 | GW | | ALL |
| W3516 | 286T3516 | | | ENGINE-S2A-FIRE DETECTION | | | | | | | | | | | |
| 451R | 16 | 9P | | | 3-11 | 26-11-12 | D04200P | | 1 | | TS0684 | A/1 | G3 | | ALL |
| 452R | 16 | 9P | | | 12-0 | 26-11-11 | D04200P | | 2 | | TS0683 | A/1 | G3 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W3510
Page 2 End
Feb 06/2009



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3520 | 286T3520 | | | ENGINE-S2B-FIRE DET | | | | | | | | | | | | |
| 451R | 16 | | 9P | 7-0 | 26-11-12 | TS0684 | B/2 | G3 | | D04154P | | 1 | | 050-099, 150-199 | | |
| 451R | 16 | | 9P | 6-0 | 26-11-12 | TS0684 | B/2 | G3 | | D04154P | | 1 | | 275-299 | | |
| 452R | 16 | | 9P | 9-0 | 26-11-11 | TS0681 | B/2 | GW | | D04154P | | 2 | | 050-099, 150-199 | | |
| 452R | 16 | | 9P | 8-0 | 26-11-11 | TS0681 | B/2 | GW | | D04154P | | 2 | | 275-299 | | |
| W3522 | 286T3522 | | | ENGINE-S2B-FIRE DETECTION | | | | | | | | | | | | |
| 451R | 16 | | 9P | 5-0 | 26-11-12 | D04228P | | | 1 | TS0684 | B/2 | GW | | 050-099, 150-199 | | |
| 451R | 16 | | 9P | 4-0 | 26-11-12 | D04228P | | | 1 | TS0684 | B/2 | GW | | 275-299 | | |
| 452R | 16 | | 9P | 13-0 | 26-11-11 | D04228P | | | 2 | TS0683 | B/2 | GW | | 050-099, 150-199 | | |
| 452R | 16 | | 9P | 12-0 | 26-11-11 | D04228P | | | 2 | TS0683 | B/2 | GW | | 275-299 | | |
| W3526 | 286T3526 | | | RH ENGINE COWL THRUST REVERSER | | | | | | | | | | | | |
| 01TB | 20 | FL | A | 7-9 | 78-34-11 | D04182P | | | 1 | SP00746 | | | 8 | ALL | | |
| 01TI | | | A | 0-0 | 78-34-11 | D04182P | | | 3 | SP00746 | DED | | | ALL | | |
| 01TO | | | A | 0-0 | 78-34-11 | D04182P | = CC | G7 | | GD06661 | S.. | GW | | ALL | | |
| 01TR | 20 | FL | A | 0-0 | 78-34-11 | D04182P | | | 2 | SP00748 | | | 8 | ALL | | |
| 101 | 18 | HP | DY | 12-6 | 78-34-11 | D07170P | | | 1 | D20196 | | 1 | | ALL | | |
| 101Z | | | DY | 0-0 | 78-34-11 | D07170P | = CC | G7 | | D20196 | | | | FA | | |
| 102 | 18 | HP | EA | 1-5 | 78-34-11 | GD05994 | | | D.. | GW | | 2 | | ALL | | |
| 102Z | | | EA | 0-0 | 78-34-11 | GD05994 | | | DED | | | | | FA | | |
| 103 | 18 | HL | | 1-3 | 78-34-11 | GD08310 | | | S.. | GW | *1 | 3 | | ALL | | |
| 104 | 18 | HL | | 1-3 | 78-34-11 | GD08310 | | | S.. | GW | *1 | | | FA | | |
| 201B | 20 | HQ | AC | 6-6 | 78-36-11 | D04182P | | | 5 | D08340J | | 2 | | ALL | | |
| 201R | 20 | HQ | AC | 0-0 | 78-36-11 | D04182P | | | 4 | D08340J | | 1 | | ALL | | |
| 201Z | | | AC | 0-0 | 78-36-11 | D04182P | = CC | G7 | | D08340J | = CC | G7 | | ALL | | |
| 203B | 20 | HQ | AB | 6-6 | 78-36-11 | D04182P | | | 7 | D08340J | | 3 | | ALL | | |
| 203R | 20 | HQ | AB | 0-0 | 78-36-11 | D04182P | | | 6 | D08340J | | 4 | | ALL | | |
| 203Z | | | AB | 0-0 | 78-36-11 | D04182P | = CC | G7 | | D08340J | = CC | G7 | | ALL | | |
| A-A | | | | 0-0 | 78-34-11 | S01605 | | | BLU | | | 8 | | ALL | | |
| A-B | | | | 0-0 | 78-34-11 | S01605 | | | RED | | | 8 | | ALL | | |
| W3528 | 286T3528 | | | LH ENGINE COWL THRUST REVERSER | | | | | | | | | | | | |
| 01TB | 20 | FL | A | 7-11 | 78-34-11 | D04180P | | | 1 | SP00742 | | | 8 | ALL | | |
| 01TI | | | A | 0-0 | 78-34-11 | D04180P | | | 3 | SP00742 | DED | | | ALL | | |
| 01TO | | | A | 0-0 | 78-34-11 | D04180P | = CC | G7 | | GD06663 | S.. | GW | | ALL | | |
| 01TR | 20 | FL | A | 0-0 | 78-34-11 | D04180P | | | 2 | SP00744 | | | 8 | ALL | | |
| 101 | 18 | HP | DY | 12-7 | 78-34-11 | D07172P | | | 1 | D20194 | | 1 | | ALL | | |
| 101Z | | | DY | 0-0 | 78-34-11 | D07172P | = CC | G7 | | D20194 | | | | FA | | |

WIRE LIST

D280T132

91-21-11

Section W3520

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3528 | 286T3528 | | | LH ENGINE COWL THRUST REVERSER (continued) | | | | | | | | | | | |
| 102 | 18 | HP | | EA | 1-6 | 78-34-11 | GD05996 | D.. | GW | | D20194 | | 2 | | ALL |
| 102Z | | | | EA | 0-0 | 78-34-11 | GD05996 | DED | | | D20194 | | | FA | ALL |
| 103 | 18 | HL | | | 1-8 | 78-34-11 | GD08308 | S.. | GW | *1 | D20194 | | 3 | | ALL |
| 104 | 18 | HL | | | 1-8 | 78-34-11 | GD08308 | S.. | GW | *1 | D20194 | | | FA | ALL |
| 201B | 20 | HQ | AI | | 7-0 | 78-36-11 | D04180P | | 5 | | D08338J | | 2 | | ALL |
| 201R | 20 | HQ | AI | | 0-0 | 78-36-11 | D04180P | | 4 | | D08338J | | 1 | | ALL |
| 201Z | | | AI | | 0-0 | 78-36-11 | D04180P | =CC | G7 | | D08338J | =CC | G7 | | ALL |
| 203B | 20 | HQ | AJ | | 7-0 | 78-36-11 | D04180P | | 7 | | D08338J | | 4 | | ALL |
| 203R | 20 | HQ | AJ | | 0-0 | 78-36-11 | D04180P | | 6 | | D08338J | | 3 | | ALL |
| 203Z | | | AJ | | 0-0 | 78-36-11 | D04180P | =CC | G7 | | D08338J | =CC | G7 | | ALL |
| A-A | | | | | 0-0 | 78-34-11 | S01604 | BLU | | | SP00742 | | 8 | | ALL |
| A-B | | | | | 0-0 | 78-34-11 | S01604 | RED | | | SP00744 | | 8 | | ALL |

WIRE LIST
D280T132

91-21-11
Section W3520
Page 2 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|----|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W3530 | 286T3530 | | | LH ENGINE COWL THRUST REVERSER | | | | | | | | | | | | | |
| 005 | 20 | HP | AE | 8-0 | 75-23-11 | D04192P | | 5 | | | | | D08314 | 1 | | | ALL |
| 005Z | | | AE | 0-0 | 75-23-11 | D04192P | =CC | | GW | | | | GD06655 | S.. | GW | | ALL |
| 006 | 18 | HP | AF | 7-0 | 75-23-11 | SM00009 | | | VH | | | | D08314 | 5 | | | ALL |
| 006Z | | | AF | 0-0 | 75-23-11 | SM00009 | REF | | | VH | | | GD06657 | S.. | GW | | ALL |
| 007 | 20 | HP | AG | 8-0 | 75-23-11 | D04192P | | 7 | | | | | D08314 | 2 | | | ALL |
| 007Z | | | AG | 0-0 | 75-23-11 | GD06655 | S.. | | GW | | | | D04192P | =CC | GW | | ALL |
| 008 | 20 | HP | AH | 8-0 | 75-23-11 | D04192P | | 6 | | | | | D08314 | 8 | | | ALL |
| 008Z | | | AH | 0-0 | 75-23-11 | GD06655 | S.. | | GW | | | | D04192P | =CC | GW | | ALL |
| 011 | 18 | HP | AK | 7-0 | 75-23-11 | SM00009 | | | VH | | | | D08314 | 7 | | | ALL |
| 011Z | | | AK | 0-0 | 75-23-11 | SM00009 | REF | | | VH | | | GD06657 | S.. | GW | | ALL |
| 012 | 20 | HP | AL | 8-0 | 75-23-11 | D04192P | | 8 | | | | | D08314 | 4 | | | ALL |
| 012Z | | | AL | 0-0 | 75-23-11 | GD06655 | S.. | | GW | | | | D04192P | =CC | GW | | ALL |
| 013 | 16 | HP | AM | 8-0 | 75-23-11 | D04192P | | 9 | | | | | D08314 | 6 | | | ALL |
| 013Z | | | AM | 0-0 | 75-23-11 | GD06657 | S.. | | GW | | | | D04192P | =CC | GW | | ALL |
| 017 | 18 | HP | AQ | 1-8 | 75-23-11 | D04192P | | 10 | | | | | SM00009 | | VH | | ALL |
| 017Z | | | AQ | 0-0 | 75-23-11 | D04192P | =CC | | GW | | | | SM00009 | REF | | VH | ALL |
| 01TB | 20 | FL | A | 9-5 | 78-36-11 | D04192P | | 11 | | | | | NL0118 | REF | | | ALL |
| 01TI | | | A | 0-0 | 78-36-11 | D04192P | | 1 | | | | | NL0118 | REF | | | ALL |
| 01TO | | | A | 0-0 | 78-36-11 | D04192P | =CC | | GW | | | | GD06645 | S.. | GW | | ALL |
| 01TR | 20 | FL | A | 0-0 | 78-36-11 | D04192P | | 12 | | | | | NL0118 | REF | | | ALL |
| 02TB | 20 | FL | B | 9-5 | 78-36-11 | D04192P | | 13 | | | | | NL0124 | REF | | | ALL |
| 02TI | | | B | 0-0 | 78-36-11 | D04192P | | 2 | | | | | NL0124 | REF | | | ALL |
| 02TO | | | B | 0-0 | 78-36-11 | D04192P | =CC | | GW | | | | GD06645 | S.. | GW | | ALL |
| 02TR | 20 | FL | B | 0-0 | 78-36-11 | D04192P | | 14 | | | | | NL0124 | REF | | | ALL |
| 201B | 20 | HQ | AU | 7-0 | 78-36-11 | D04192P | | 16 | | | | | D08342J | 2 | | | ALL |
| 201R | 20 | HQ | AU | 0-0 | 78-36-11 | D04192P | | 15 | | | | | D08342J | 1 | | | ALL |
| 201Z | | | AU | 0-0 | 78-36-11 | D04192P | =CC | | GW | | | | D08342J | =CC | G7 | | ALL |
| 203B | 20 | HQ | AV | 7-0 | 78-36-11 | D04192P | | 18 | | | | | D08342J | 4 | | | ALL |
| 203R | 20 | HQ | AV | 0-0 | 78-36-11 | D04192P | | 17 | | | | | D08342J | 3 | | | ALL |
| 203Z | | | AV | 0-0 | 78-36-11 | D04192P | =CC | | GW | | | | D08342J | =CC | G7 | | ALL |
| W3532 | 286T3532 | | | RH ENGINE COWL THRUST REVERSER | | | | | | | | | | | | | |
| 010 | 18 | HL | | 3-3 | 78-36-11 | NL0124 | REF | | | FA | | | GD06641 | S.. | GW | | ALL |
| 011 | 18 | HL | | 3-5 | 78-36-11 | NL0118 | REF | | | FB | | | GD06641 | S.. | GW | | ALL |
| 01TB | 20 | FL | A | 8-5 | 78-36-11 | D04194P | | 4 | | | | | NL0124 | REF | | | ALL |
| 01TI | | | A | 0-0 | 78-36-11 | D04194P | | 9 | | | | | NL0124 | REF | | | ALL |
| 01TO | | | A | 0-0 | 78-36-11 | D04194P | =CC | | G7 | | | | NL0124 | REF | | FA | ALL |
| 01TR | 20 | FL | A | 0-0 | 78-36-11 | D04194P | | 5 | | | | | NL0124 | REF | | | ALL |
| 02TB | 20 | FL | B | 8-7 | 78-36-11 | D04194P | | 6 | | | | | NL0118 | REF | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W3530

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3532 | 286T3532 | | | RH ENGINE COWL THRUST REVERSER (continued) | | | | | | | | | | | |
| 02TI | | | | B | 0-0 | 78-36-11 | D04194P | 8 | | | NL0118 | REF | | | ALL |
| 02TO | | | | B | 0-0 | 78-36-11 | D04194P | = CC | G7 | | NL0118 | REF | | FB | ALL |
| 02TR | 20 | FL | | B | 0-0 | 78-36-11 | D04194P | 7 | | | NL0118 | REF | | | ALL |
| 201B | 20 | HQ | | AF | 6-6 | 78-36-11 | D04194P | 2 | | | D08344J | 2 | | | ALL |
| 201R | 20 | HQ | | AF | 0-0 | 78-36-11 | D04194P | 3 | | | D08344J | 1 | | | ALL |
| 201Z | | | | AF | 0-0 | 78-36-11 | D04194P | = CC | G7 | | D08344J | = CC | G7 | | ALL |
| 203B | 20 | HQ | | AE | 6-6 | 78-36-11 | D04194P | 10 | | | D08344J | 3 | | | ALL |
| 203R | 20 | HQ | | AE | 0-0 | 78-36-11 | D04194P | 1 | | | D08344J | 4 | | | ALL |
| 203Z | | | | AE | 0-0 | 78-36-11 | D04194P | = CC | G7 | | D08344J | = CC | G7 | | ALL |
| W3538 | 286T3538 | | | ENGINE-IDG CONTROL | | | | | | | | | | | |
| 001 | 18 | HL | | | 9-4 | 24-11-11 | D04216P | 4 | | | D10966 | 4 | | | ALL |
| 002 | 18 | HL | | | 7-7 | 24-11-11 | GD06585 | D.. | GW | | D10966 | 6 | | | ALL |
| 003 | 18 | HL | | | 10-11 | 24-11-11 | D04216P | 16 | | | D10964 | 9 | | | ALL |
| 004 | 18 | HL | | | 10-11 | 24-11-11 | D04216P | 17 | | | D10964 | 11 | | | ALL |
| 005 | 18 | HL | | | 9-2 | 24-11-11 | GD06585 | D.. | GW | | D10964 | 10 | | | ALL |
| 006 | 18 | HL | | | 9-0 | 24-11-11 | GD06617 | S.. | GW | | D10964 | 12 | | | ALL |
| 007 | 20 | HP | Y | | 8-6 | 24-11-11 | D04216P | 21 | | | D11536 | B | | | ALL |
| 007Z | | | Y | | 0-0 | 24-11-11 | D04216P | DED | | | D11536 | DED | | | ALL |
| 008 | 20 | HP | AH | | 7-2 | 24-11-11 | GD06583 | D.. | GW | | D11046 | G | | | ALL |
| 008Z | | | AH | | 0-0 | 24-11-11 | D11046 | DED | | | GD06583 | DED | | | ALL |
| 009 | 20 | HP | AI | | 7-2 | 24-11-11 | GD06583 | D.. | GW | | D11046 | F | | | ALL |
| 009Z | | | AI | | 0-0 | 24-11-11 | D11046 | DED | | | GD06583 | DED | | | ALL |
| 010 | 20 | HP | AJ | | 10-1 | 24-11-11 | D11046 | E | | | D04216P | 22 | | | ALL |
| 010Z | | | AJ | | 0-0 | 24-11-11 | D11046 | DED | | | D04216P | DED | | | ALL |
| 011 | 20 | HP | AK | | 7-2 | 24-11-11 | GD06583 | D.. | GW | | D11046 | A | | | ALL |
| 011Z | | | AK | | 0-0 | 24-11-11 | D11046 | DED | | | GD06583 | DED | | | ALL |
| 012 | 20 | HP | AL | | 10-1 | 24-11-11 | D11046 | B | | | D04216P | 27 | | | ALL |
| 012Z | | | AL | | 0-0 | 24-11-11 | D11046 | DED | | | D04216P | DED | | | ALL |
| 013 | 20 | HP | H | | 8-6 | 24-11-11 | D04216P | 28 | | | D11536 | C | | | ALL |
| 013Z | | | H | | 0-0 | 24-11-11 | D04216P | DED | | | D11536 | DED | | | ALL |
| 014 | 20 | HP | AN | | 7-0 | 24-11-11 | GD06619 | S.. | GW | | D11046 | J | | | ALL |
| 014Z | | | AN | | 0-0 | 24-11-11 | D11046 | DED | | | GD06619 | DED | | | ALL |
| 015 | 18 | HL | | | 9-4 | 24-11-11 | D04216P | 23 | | | D10966 | 7 | | | ALL |
| 016 | 18 | HL | | | 9-4 | 24-11-11 | D04216P | 24 | | | D10966 | 8 | | | ALL |
| 017 | 20 | HP | J | | 7-11 | 24-11-11 | D11536 | A | | | D11046 | H | | | ALL |
| 017Z | | | J | | 0-0 | 24-11-11 | D11536 | DED | | | D11046 | DED | | | ALL |
| 201B | 18 | HQ | A | | 9-4 | 24-11-11 | D04216P | 1 | | | D10966 | 1 | | | ALL |
| 201R | 18 | HQ | A | | 0-0 | 24-11-11 | D04216P | 2 | | | D10966 | 2 | | | ALL |

WIRE LIST

D280T132

91-21-11
 Section W3530
 Page 2
 Mar 09/2006



| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | |
|--------------|-----------------|----|-------|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|------|--------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W3538 | 286T3538 | | | ENGINE-IDG CONTROL (continued) | | | | | | | | | | |
| 201Z | | | A | 0-0 | 24-11-11 | D04216P | | 3 | | D10966 | DED | | | ALL |
| 202B | 18 | HQ | B | 9-4 | 24-21-11 | D04216P | | 5 | | D10966 | | 9 | | ALL |
| 202R | 18 | HQ | B | 0-0 | 24-21-11 | D04216P | | 6 | | D10966 | | 10 | | ALL |
| 202Z | | | B | 0-0 | 24-21-11 | D04216P | | 7 | | D10966 | DED | | | ALL |
| 203B | 18 | HM | D | 10-11 | 24-11-11 | D04216P | | 12 | | D10964 | | 4 | | ALL |
| 203R | 18 | HM | D | 0-0 | 24-11-11 | D04216P | | 13 | | D10964 | | 5 | | ALL |
| 204B | 18 | HM | E | 10-11 | 24-11-11 | D04216P | | 14 | | D10964 | | 6 | | ALL |
| 204R | 18 | HM | E | 0-0 | 24-11-11 | D04216P | | 15 | | D10964 | | 7 | | ALL |
| 301B | 18 | HN | F | 10-11 | 24-21-11 | D04216P | | 18 | | D10964 | | 1 | | ALL |
| 301R | 18 | HN | F | 0-0 | 24-21-11 | D04216P | | 19 | | D10964 | | 2 | | ALL |
| 301Y | 18 | HN | F | 0-0 | 24-21-11 | D04216P | | 20 | | D10964 | | 3 | | ALL |
| 401B | 18 | HT | C | 9-4 | 24-21-11 | D04216P | | 8 | | D10966 | | 12 | | ALL |
| 401G | 18 | HT | C | 0-0 | 24-21-11 | D04216P | | 11 | | D10966 | | 3 | | ALL |
| 401R | 18 | HT | C | 0-0 | 24-21-11 | D04216P | | 9 | | D10966 | | 13 | | ALL |
| 401Y | 18 | HT | C | 0-0 | 24-21-11 | D04216P | | 10 | | D10966 | | 14 | | ALL |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--------------------------|----------|---------|------|------|--------|-------|------|--------|--------|-------------|-----|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3540 | 286T3540 | | | | ENGINE-PNEUMATICS | | | | | | | | | | | |
| 001 | 18 | | HL | | 1-10 | 36-23-11 | D04156P | | 1 | | | | V00348 | 1 | GW | ALL |
| 002 | 18 | | HL | | 1-10 | 36-23-11 | D04156P | | 2 | | | | V00348 | 2 | GW | ALL |
| 003 | 18 | | HL | | 1-10 | 36-23-11 | D04156P | | 3 | | | | V00348 | 3 | GW | ALL |
| W3542 | 286T3542 | | | | ENGINE-PT2/TT2 | | | | | | | | | | | |
| 101 | 16 | | HP | A | 2-9 | 30-34-11 | D08316J | | 2 | | | | D11434 | 2 | | ALL |
| 101Z | | | | A | 0-0 | 30-34-11 | D08316J | =CC | G7 | | | | D11434 | =CC | G7 | ALL |
| 102 | 16 | | HP | C | 2-9 | 30-34-11 | D08316J | | 1 | | | | D11434 | 3 | | ALL |
| 102Z | | | | C | 0-0 | 30-34-11 | D08316J | =CC | G7 | | | | D11434 | =CC | G7 | ALL |
| 301B | 20 | | HR | B | 2-11 | 73-21-12 | D08332J | | 2 | | | | D11434 | 6 | | ALL |
| 301R | 20 | | HR | B | 0-0 | 73-21-12 | D08332J | | 1 | | | | D11434 | 5 | | ALL |
| 301Y | 20 | | HR | B | 0-0 | 73-21-12 | D08332J | | 3 | | | | D11434 | 7 | | ALL |
| 301Z | | | | B | 0-0 | 73-21-12 | D08332J | =CC | G7 | | | | D11434 | =CC | G7 | ALL |
| W3544 | 286T3544 | | | | ENGINE-PT2/TT2 | | | | | | | | | | | |
| 301B | 20 | | HR | B | 2-11 | 73-21-12 | D08328J | | 3 | | | | D11420 | 3 | | ALL |
| 301R | 20 | | HR | B | 0-0 | 73-21-12 | D08328J | | 2 | | | | D11420 | 2 | | ALL |
| 301Y | 20 | | HR | B | 0-0 | 73-21-12 | D08328J | | 1 | | | | D11420 | 1 | | ALL |
| 301Z | | | | B | 0-0 | 73-21-12 | D08328J | =CC | G7 | | | | D11420 | =CC | G7 | ALL |

WIRE LIST
D280T132

91-21-11
Section W3540
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|---------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|--|-----------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W5150 | 286T5150 | | | P10 QUADRANT STAND | | | | | | | | | | | | | | |
| 024 | 20 | | PA | 0-0 | 33-13-18 | TB0217H | | 4 | 2 | | | | QD6776P | = 1 | | | | 050-099, 155, 162-165, 275-276 |
| 025 | 20 | | PA | 0-0 | 33-13-18 | QD6780J | | = 1 | | | | | GD00609 | A.. | 2 | | | 050-099, 155, 162-165, 275-276 |
| 026 | 20 | | PA | 0-0 | 33-13-18 | QD6776J | | = 1 | | | | | L01165 | = P | B | | | 050-099, 155, 162-165, 275-276 |
| 027 | 20 | | PA | 0-0 | 33-13-18 | QD6780P | | = 1 | | | | | L01165 | = G | G | | | 050-099, 155, 162-165, 275-276 |
| 200 | 22 | | PA | 0-0 | 76-11-11 | D01469 | | 24 | | | | | D08118J | 1 | | | | ALL |
| 201 | 22 | | PA | 0-0 | 33-16-18 | D01469 | | 4 | | | | | D08118J | 23 | | | | ALL |
| 202 | 22 | | PA | 0-0 | 33-16-18 | D01469 | | 3 | | | | | D08118J | 22 | | | | ALL |
| 203 | 22 | | PA | 0-0 | 76-11-11 | D01469 | | 5 | | | | | D08118J | 3 | | | | ALL |
| 204 | 22 | | PA | 0-0 | 26-11-11 | D01469 | | 6 | | | | | D08118J | 15 | | | | ALL |
| 205 | 22 | | PA | 0-0 | 76-11-11 | D01469 | | 7 | | | | | D08118J | 10 | | | | ALL |
| 206 | 22 | | PA | 0-0 | SPARE | D01469 | | 8 | | | | | D08118J | 13 | | | | 050-099, 275-299 |
| 207 | 22 | | PA | 0-0 | 76-11-11 | D01469 | | 9 | | | | | D08118J | 2 | | | | ALL |
| 208 | 22 | | PA | 0-0 | 73-21-11 | D08118J | | 4 | | | | | D01469 | 10 | | | | 050-099 |
| 208 | 22 | | PA | 0-0 | 73-21-11 | D01469 | | 10 | | | | | D08118J | 4 | | | | 150-199, 275-299 |
| 209 | 22 | | PA | 0-0 | 28-22-21 | D01469 | | 11 | | | | | D08118J | 16 | | | | ALL |
| 210 | 22 | | PA | 0-0 | 28-22-21 | D01469 | | 12 | | | | | D08118J | 19 | | | | ALL |
| 211 | 22 | | PA | 0-0 | 28-22-21 | D01469 | | 13 | | | | | D08118J | 18 | | | | ALL |
| 212 | 22 | | PA | 0-0 | 28-22-21 | D01469 | | 14 | | | | | D08118J | 26 | | | | ALL |
| 213 | 20 | | PA | 0-0 | 28-22-21 | D01469 | | 15 | | | | | GD00002 | D.. | 2 | | | ALL |
| 214 | 22 | | PA | 0-0 | SPARE | D01469 | | 17 | | | | | D08118J | 14 | | | | 150-199 |
| 215 | 20 | | PA | 0-0 | SPARE | D01469 | | 18 | | | | | D08118J | 11 | | | | 050-099, 150-154, 275-299 |
| 215 | 20 | | PA | 0-0 | 73-21-11 | D01469 | | 18 | | | | | D08118J | 11 | | | | 155-199 |
| 216 | 20 | | PA | 0-0 | 27-41-11 | D01469 | | 26 | | | | | D08118J | 17 | | | | ALL |
| 217 | 20 | | PA | 0-0 | 27-41-11 | D01469 | | 25 | | | | | D04551J | 1 | | | | ALL |
| 218 | 20 | | PA | 0-0 | 27-41-11 | D01469 | | 27 | | | | | D04551J | 2 | | | | ALL |
| 219 | 22 | | PA | 0-0 | 28-22-21 | D01469 | | 23 | | | | | D08120J | 11 | | | | ALL |
| 220 | 22 | | PA | 0-0 | SPARE | D01469 | | 16 | | | | | D08120J | 2 | | | | 050-099, 150-154, 275-299 |
| 220 | 22 | | PA | 0-0 | 73-21-11 | D01469 | | 16 | | | | | D08120J | 2 | | | | 155-199 |
| 221 | 22 | | PA | 0-0 | 75-24-11 | D01469 | | 19 | | | | | D08120J | 8 | | | | 150-157 |
| 221 | 22 | | PA | 0-0 | SPARE | D01469 | | 19 | | | | | D08120J | 8 | | | | 162-199 |
| 222 | 22 | | PA | 0-0 | 75-24-11 | D01469 | | 20 | | | | | D08120J | 16 | | | | 150-157 |
| 222 | 22 | | PA | 0-0 | SPARE | D01469 | | 20 | | | | | D08120J | 16 | | | | 162-199 |

WIRE LIST

D280T132

91-21-11

Section W5150

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5150 | 286T5150 | | | P10 QUADRANT STAND (continued) | | | | | | | | | | | |
| 223 | 22 | | PA | 0-0 | SPARE | D01469 | | 21 | | | D08120J | | 15 | | 050-099, 150-154, 275-299 |
| 223 | 22 | | PA | 0-0 | 73-21-11 | D01469 | | 21 | | | D08120J | | 15 | | 155-199 |
| 224 | 22 | | PA | 0-0 | SPARE | D01469 | | 22 | | | D08120J | | 1 | | 050-099, 150-154, 275-299 |
| 224 | 22 | | PA | 0-0 | 73-21-11 | D01469 | | 22 | | | D08120J | | 1 | | 155-199 |
| 227 | 22 | | PA | 0-0 | 73-21-11 | D08118J | | 12 | | | D01469 | | 30 | | 050-099 |
| 227 | 22 | | PA | 0-0 | 73-21-11 | D01469 | | 30 | | | D08118J | | 12 | | 150-199, 275-299 |
| 228 | 22 | | PA | 0-0 | 73-21-11 | D08118J | | 7 | | | D01469 | | 31 | | ALL |
| 229B | 20 | | PB | JD | 0-0 | 33-13-18 | TB0217H | 9 | 2 | | D08118J | | 25 | | 156-157, 166-199, 277-299 |
| 229R | 20 | | PB | JD | 0-0 | 33-13-18 | TB0217H | 4 | 2 | | D08118J | | 24 | | 156-157, 166-199, 277-299 |
| 230B | 20 | | PB | JE | 0-0 | 33-13-18 | QD6780J | = 1 | | | TB0217H | | 9 | 2 | 156-157, 166-199, 277-299 |
| 230R | 20 | | PB | JE | 0-0 | 33-13-18 | TB0217H | 4 | 2 | | QD6776P | | = 1 | | 156-157, 166-199, 277-299 |
| 231B | 20 | | PB | JF | 0-0 | 33-13-18 | QD6780P | = 1 | | | L01165 | | = G | G | 156-157, 166-199, 277-299 |
| 231R | 20 | | PB | JF | 0-0 | 33-13-18 | QD6776J | = 1 | | | L01165 | | = P | B | 156-157, 166-199, 277-299 |
| 250 | 22 | | PA | 0-0 | 76-11-11 | D01471 | | 26 | | | D08114J | | 3 | | ALL |
| 251 | 22 | | PA | 0-0 | 33-16-18 | D01471 | | 3 | | | D08114J | | 13 | | ALL |
| 252 | 22 | | PA | 0-0 | 33-16-18 | D01471 | | 4 | | | D08114J | | 12 | | ALL |
| 253 | 22 | | PA | 0-0 | 76-11-11 | D01471 | | 5 | | | D08114J | | 5 | | ALL |
| 254 | 22 | | PA | 0-0 | 26-11-21 | D01471 | | 6 | | | D08114J | | 9 | | ALL |
| 255 | 22 | | PA | 0-0 | 76-11-11 | D01471 | | 7 | | | D08114J | | 1 | | ALL |
| 256 | 22 | | PA | 0-0 | SPARE | D01471 | | 8 | | | D08114J | | 16 | | 050-099, 275-299 |
| 257 | 22 | | PA | 0-0 | 76-11-11 | D01471 | | 9 | | | D08114J | | 4 | | ALL |
| 258 | 22 | | PA | 0-0 | 73-21-11 | D08114J | | 6 | | | D01471 | | 10 | | 050-099 |
| 258 | 22 | | PA | 0-0 | 73-21-11 | D01471 | | 10 | | | D08114J | | 6 | | 150-199, 275-299 |
| 259 | 22 | | PA | 0-0 | 28-22-21 | D01471 | | 11 | | | D08114J | | 10 | | ALL |
| 260 | 22 | | PA | 0-0 | 28-22-21 | D01471 | | 12 | | | D08114J | | 14 | | ALL |
| 261 | 22 | | PA | 0-0 | 28-22-21 | D01471 | | 13 | | | D08114J | | 15 | | ALL |
| 262 | 22 | | PA | 0-0 | 28-22-21 | D01471 | | 14 | | | D08114J | | 17 | | ALL |
| 263 | 20 | | PA | 0-0 | 28-22-21 | D01471 | | 15 | | | GDX0002 | | D.. | 2 | ALL |
| 264 | 22 | | PA | 0-0 | SPARE | D01471 | | 17 | | | D08114J | | 8 | | 150-199 |
| 265 | 22 | | PA | 0-0 | SPARE | D01471 | | 18 | | | D08114J | | 2 | | 150-199 |
| 266 | 20 | | PA | 0-0 | 27-41-21 | D01471 | | 24 | | | D08114J | | 11 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W5150

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W5150 | 286T5150 | | | P10 QUADRANT STAND (continued) | | | | | | | | | | | | | |
| 267 | 22 | | PA | 0-0 | 28-22-21 | D01471 | | 27 | | | | | D08116J | 11 | | | ALL |
| 268 | 22 | | PA | 0-0 | SPARE | D01471 | | 16 | | | | | D08116J | 2 | | | 050-099, 150-199 |
| 269 | 22 | | PA | 0-0 | 75-24-11 | D01471 | | 19 | | | | | D08116J | 12 | | | 150-157 |
| 269 | 22 | | PA | 0-0 | SPARE | D01471 | | 19 | | | | | D08116J | 12 | | | 162-199 |
| 270 | 22 | | PA | 0-0 | 75-24-11 | D01471 | | 20 | | | | | D08116J | 6 | | | 150-157 |
| 270 | 22 | | PA | 0-0 | SPARE | D01471 | | 20 | | | | | D08116J | 6 | | | 162-199 |
| 271 | 22 | | PA | 0-0 | SPARE | D01471 | | 22 | | | | | D08116J | 13 | | | ALL |
| 272 | 22 | | PA | 0-0 | SPARE | D01471 | | 21 | | | | | D08116J | 1 | | | 050-099, 150-154, 275-299 |
| 272 | 22 | | PA | 0-0 | 73-21-11 | D01471 | | 21 | | | | | D08116J | 1 | | | 155-199 |
| 273 | 20 | | PA | 0-0 | 27-41-21 | D01471 | | 23 | | | | | D04555J | 7 | | | ALL |
| 274 | 20 | | PA | 0-0 | 27-41-21 | D01471 | | 25 | | | | | D04555J | 4 | | | ALL |
| 277 | 22 | | PA | 0-0 | 73-21-11 | D08114J | | 21 | | | | | D01471 | 30 | | | 050-099 |
| 277 | 22 | | PA | 0-0 | 73-21-11 | D01471 | | 30 | | | | | D08114J | 21 | | | 150-199, 275-299 |
| 278 | 22 | | PA | 0-0 | 73-21-11 | D08114J | | 22 | | | | | D01471 | 31 | | | ALL |
| 300 | 22 | | PA | 0-0 | 78-34-21 | D01473 | | 9 | | | | | D08116J | 5 | | | ALL |
| 301 | 22 | | PA | 0-0 | 22-12-21 | D01473 | | 5 | | | | | D04555J | 2 | | | ALL |
| 302 | 22 | | PA | 0-0 | 22-12-21 | D01473 | | 2 | | | | | D04555J | 6 | | | ALL |
| 303 | 22 | | PA | 0-0 | 22-12-21 | D01473 | | 1 | | | | | D01473 | 6 | | | ALL |
| 304 | 22 | | PA | 0-0 | 78-34-21 | D01473 | | 7 | | | | | D08116J | 4 | | | ALL |
| 305 | 22 | | PA | 0-0 | 78-34-21 | D01473 | | 8 | | | | | D08116J | 3 | | | ALL |
| 310 | 22 | | PA | 0-0 | 22-12-31 | D01475 | | 2 | | | | | D04553J | 4 | | | ALL |
| 311 | 22 | | PA | 0-0 | 22-12-31 | D01475 | | 1 | | | | | D01475 | 6 | | | ALL |
| 312 | 22 | | PA | 0-0 | 22-12-31 | D01475 | | 5 | | | | | D04553J | 3 | | | ALL |
| 320 | 22 | | PA | 0-0 | 78-34-11 | D01477 | | 8 | | | | | D08120J | 22 | | | ALL |
| 321 | 22 | | PA | 0-0 | 78-34-11 | D01477 | | 9 | | | | | D08120J | 9 | | | ALL |
| 322 | 22 | | PA | 0-0 | 78-34-11 | D01477 | | 10 | | | | | D08120J | 24 | | | ALL |
| 323 | 22 | | PA | 0-0 | 22-32-15 | D01477 | | 1 | | | | | D04551J | 3 | | | ALL |
| 324 | 22 | | PA | 0-0 | 22-32-15 | D01477 | | 11 | | | | | SM00001 | | W | | ALL |
| 325 | 22 | | PA | 0-0 | 22-32-15 | D04551J | | 5 | | | | | SM00001 | | W | | ALL |
| 326 | 22 | | PA | 0-0 | 22-32-15 | D01477 | | 13 | | | | | SM00001 | | W | | ALL |
| 327 | 22 | | PA | 0-0 | 22-32-15 | D01477 | | 12 | | | | | SM00002 | | W | | ALL |
| 328 | 22 | | PA | 0-0 | 22-32-15 | D04551J | | 4 | | | | | SM00002 | | W | | ALL |
| 329 | 22 | | PA | 0-0 | 22-32-15 | D01477 | | 14 | | | | | SM00002 | | W | | ALL |
| 330 | 22 | | PA | 0-0 | 22-32-15 | D01477 | | 7 | | | | | SM00002 | | W | | ALL |
| 331 | 22 | | PA | 0-0 | 22-12-11 | D01477 | | 4 | | | | | D04551J | 22 | | | ALL |
| 332 | 22 | | PA | 0-0 | 22-12-11 | D01477 | | 3 | | | | | D01477 | 15 | | | ALL |
| 333 | 22 | | PA | 0-0 | 22-12-11 | D01477 | | 5 | | | | | D04551J | 21 | | | ALL |
| 334 | 22 | | PA | 0-0 | 22-32-15 | D01477 | | 2 | | | | | D01477 | 6 | | | ALL |

WIRE LIST

D280T132

91-21-11

Section W5150

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|------|----|---|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W5150 | 286T5150 | | | P10 QUADRANT STAND (continued) | | | | | | | | | | | | | | | |
| 350 | 20 | | PA | | 0-0 | 27-62-11 | D01479 | | | | 12 | | | | GD00605 | S.. | E | | ALL |
| 351 | 20 | | PA | | 0-0 | 27-62-11 | D01479 | | | | 10 | | | | GD00601 | D.. | 2 | | ALL |
| 352 | 20 | | PA | | 0-0 | 27-62-11 | D01479 | | | | 6 | | | | D08120J | | 21 | | ALL |
| 353 | 20 | | PA | | 0-0 | 27-62-11 | D01479 | | | | 8 | | | | D08120J | | 23 | | ALL |
| 354 | 20 | | PA | | 0-0 | 27-62-11 | D01479 | | | | 4 | | | | GD00601 | D.. | 2 | | ALL |
| 355 | 22 | | PA | | 0-0 | 27-62-11 | D01479 | | | | 3 | | | | TB0219F | A003 | 2 | | ALL |
| 356 | 22 | | PA | | 0-0 | 27-62-11 | TB0219F | C003 | 2 | | | | | | D08116J | | 22 | | ALL |
| 357 | 22 | | PA | | 0-0 | 27-62-11 | TB0219F | A004 | 2 | | | | | | D08116J | | 21 | | ALL |
| 358 | 22 | | PA | | 0-0 | 27-62-11 | TB0219F | C004 | 2 | | | | | | D08120J | | 3 | | ALL |
| 359 | 22 | | PA | | 0-0 | 27-62-11 | TB0219G | | 6 | 2 | | | | | D08120J | | 14 | | ALL |
| 360 | 22 | | PA | | 0-0 | 27-62-11 | TB0215G | | 15 | 2 | | | | | D08120J | | 12 | | ALL |
| 361 | 22 | | PA | | 0-0 | 27-62-11 | TB0215G | | 15 | 2 | | | | | D08120J | | 4 | | ALL |
| 364 | 20 | | PA | | 0-0 | 22-12-11 | S00521 | | C | \$ | | | | | GD00002 | D.. | 2 | | ALL |
| 365 | 22 | | PA | | 0-0 | 22-12-11 | S00521 | | NC | \$ | | | | | TB0215F | A008 | 2 | | ALL |
| 367 | 22 | | PA | | 0-0 | 22-12-11 | TB0215F | | A008 | 2 | | | | | D04551J | | 23 | | ALL |
| 368 | 22 | | PA | | 0-0 | 22-32-13 | TB0215F | | C008 | 2 | | | | | D04551J | | 12 | | ALL |
| 369 | 22 | | PA | | 0-0 | 22-32-13 | S00312 | | NC | \$ | | | | | TB0215F | C008 | 2 | | ALL |
| 370 | 22 | | PA | | 0-0 | 22-32-13 | S00312 | | C | \$ | | | | | TB0215F | A009 | 2 | | ALL |
| 371 | 22 | | PA | | 0-0 | 22-32-13 | S00312 | | NO | \$ | | | | | TB0215F | C009 | 2 | | ALL |
| 372 | 22 | | PA | | 0-0 | 22-32-13 | TB0215F | | A009 | 2 | | | | | D04551J | | 13 | | ALL |
| 373 | 22 | | PA | | 0-0 | 22-32-13 | TB0215F | | C009 | 2 | | | | | D04551J | | 14 | | ALL |
| 374 | 22 | | PA | | 0-0 | 27-41-11 | TB0217G | | 1 | 2 | | | | | D04551J | | 16 | | 150-154 |
| 376 | 20 | | PA | | 0-0 | 22-12-21 | S00522 | | C | \$ | | | | | GD00002 | D.. | 2 | | ALL |
| 377 | 22 | | PA | | 0-0 | 22-12-21 | S00522 | | NC | \$ | | | | | TB0215G | | 11 | 2 | ALL |
| 380 | 22 | | PA | | 0-0 | 22-12-21 | TB0215G | | 11 | 2 | | | | | D04555J | | 1 | | ALL |
| 382 | 20 | | PA | | 0-0 | 22-12-31 | S00523 | | C | \$ | | | | | GD00002 | D.. | 2 | | ALL |
| 383 | 22 | | PA | | 0-0 | 22-12-31 | S00523 | | NC | \$ | | | | | TB0215G | | 13 | 2 | ALL |
| 386 | 22 | | PA | | 0-0 | 22-12-31 | TB0215G | | 13 | 2 | | | | | D04553J | | 5 | | ALL |
| 387 | 22 | | PA | | 0-0 | 32-44-11 | L00592 | | 2 | 1A | | | | | TB0219F | A001 | 2 | | ALL |
| 388 | 22 | | PA | | 0-0 | 33-16-18 | L00592 | | 3 | 1A | | | | | TB0219F | C001 | 2 | | ALL |
| 389 | 22 | | PA | | 0-0 | 33-16-18 | L00592 | | 1 | 1A | | | | | TB0219G | | 2 | 2 | ALL |
| 390 | 20 | | PA | | 0-0 | 33-13-18 | TB0217G | | 2 | 2 | | | | | D08116J | | 10 | | ALL |
| 391 | 20 | | PA | | 0-0 | 33-13-18 | TB0217H | | 4 | 2 | | | | | D08118J | | 24 | | 050-099, 150-155, 162-165, 275-276 |
| 392 | 20 | | PA | | 0-0 | 33-13-18 | TB0217G | | 3 | 2 | | | | | D08120J | | 10 | | ALL |
| 396 | 22 | | PA | | 0-0 | 31-51-42 | D04551J | | 18 | | | | | | D08120J | | 13 | | ALL |
| 397 | 22 | | PA | | 0-0 | SPARE | D04551J | | 17 | | | | | | D08120J | | 7 | | ALL |
| 398 | 22 | | PA | | 0-0 | 27-62-11 | D08120J | | 6 | | | | | | D08120J | | 5 | | ALL |
| 399 | 22 | | PA | | 0-0 | 32-42-12 | D08120J | | 36 | | | | | | D08120J | | 35 | | ALL |

WIRE LIST
D280T132



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W5150 | 286T5150 | | | P10 QUADRANT STAND (continued) | | | | | | | | | | | | | |
| 400 | 22 | | PA | 0-0 | 32-42-12 | D08120J | | 38 | | | | | D08120J | 39 | | | ALL |
| 401 | 22 | | PA | 0-0 | 32-42-12 | TB0219H | | 9 | 2 | | | | D08120J | 20 | | | ALL |
| 402 | 22 | | PA | 0-0 | 32-42-12 | TB0219H | | 9 | 2 | | | | D08120J | 40 | | | ALL |
| 403 | 22 | | PA | 0-0 | 32-42-12 | SM00003 | | | | W | | | D08120J | 37 | | | ALL |
| 404 | 22 | | PA | 0-0 | 32-42-12 | SM00003 | | | | W | | | D08116J | 15 | | | ALL |
| 405 | 22 | | PA | 0-0 | 32-42-12 | SM00003 | | | | W | | | D08116J | 17 | | | ALL |
| 406 | 22 | | PA | 0-0 | 32-42-12 | TB0219H | | 9 | 2 | | | | D08116J | 7 | | | ALL |
| 407 | 22 | | PA | 0-0 | 32-42-12 | D08116J | | 8 | | | | | D08116J | 9 | | | ALL |
| 408 | 22 | | PA | 0-0 | 32-42-12 | D08116J | | 14 | | | | | D08116J | 16 | | | ALL |
| 409 | 22 | | PA | 0-0 | 32-42-12 | TB0219G | | 8 | 2 | | | | D08120J | 41 | | | ALL |
| 410 | 22 | | PA | 0-0 | SPARE | D08116J | | 18 | | | | | D04555J | 9 | | | ALL |
| 411 | 22 | | PA | 0-0 | 31-51-42 | D08116J | | 19 | | | | | D04555J | 10 | | | ALL |
| 412 | 22 | | PA | 0-0 | 31-51-41 | TB0219F | | A007 | 2 | | | | D04555J | 5 | | | ALL |
| 413 | 22 | | PA | 0-0 | 27-51-31 | TB0215F | | A001 | 2 | | | | D08120J | 25 | | | ALL |
| 414 | 22 | | PA | 0-0 | 27-51-31 | TB0215F | | C001 | 2 | | | | D08120J | 26 | | | ALL |
| 415 | 22 | | PA | 0-0 | 27-51-31 | TB0215F | | A002 | 2 | | | | D08120J | 27 | | | ALL |
| 416 | 22 | | PA | 0-0 | 27-51-31 | TB0215F | | C002 | 2 | | | | D08120J | 28 | | | ALL |
| 417 | 22 | | PA | 0-0 | 27-51-31 | TB0215G | | 3 | 2 | | | | D08120J | 29 | | | ALL |
| 418 | 22 | | PA | 0-0 | 27-58-31 | TB0215F | | A004 | 2 | | | | D08120J | 30 | | | ALL |
| 419 | 22 | | PA | 0-0 | 27-58-31 | TB0215F | | C004 | 2 | | | | D08120J | 31 | | | ALL |
| 420 | 22 | | PA | 0-0 | 27-58-31 | TB0215F | | A005 | 2 | | | | D08120J | 32 | | | ALL |
| 421 | 22 | | PA | 0-0 | 27-58-31 | TB0215F | | C005 | 2 | | | | D08120J | 33 | | | ALL |
| 422 | 22 | | PA | 0-0 | 27-58-31 | TB0215G | | 6 | 2 | | | | D08120J | 34 | | | ALL |
| 423 | 22 | | PA | 0-0 | 32-44-11 | TB0219F | | A001 | 2 | | | | D08118J | 5 | | | ALL |
| 424 | 22 | | PA | 0-0 | 33-16-18 | TB0219F | | C001 | 2 | | | | D08118J | 21 | | | ALL |
| 425 | 22 | | PA | 0-0 | 33-16-18 | TB0219G | | 2 | 2 | | | | D08118J | 20 | | | ALL |
| 426 | 22 | | PA | 0-0 | 27-62-11 | TB0215F | | A014 | 2 | | | | TB0219G | 5 | 2 | | ALL |
| 427 | 22 | | PA | 0-0 | 27-62-11 | TB0215F | | C014 | 2 | | | | TB0219G | 6 | 2 | | ALL |
| 428 | 22 | | PA | 0-0 | 29-11-32 | TB0219F | | C007 | 2 | | | | D08118J | 8 | | | ALL |
| 429 | 22 | | PA | 0-0 | 31-31-15 | D04551J | | 10 | | | | | TB0215F | C017 | 2 | | 150-154 |
| 433 | 22 | | PA | 0-0 | 78-36-11 | D01471 | | 28 | | | | | D08116J | 20 | | | ALL |
| A-A | | | | 0-0 | 27-62-11 | S00371 | | ANC | | | | | TB0219F | A003 | 2 | | ALL |
| A-B | | | | 0-0 | 27-62-11 | S00371 | | ACM | | | | | TB0219F | C003 | 2 | | ALL |
| A-C | | | | 0-0 | 27-62-11 | S00371 | | ANO | | | | | TB0219F | A004 | 2 | | ALL |
| A-D | | | | 0-0 | 27-62-11 | S00371 | | BNC | | | | | TB0219G | 5 | 2 | | ALL |
| A-E | | | | 0-0 | 27-62-11 | S00371 | | BCM | | | | | TB0219F | C004 | 2 | | ALL |
| A-F | | | | 0-0 | 27-62-11 | S00371 | | BNO | | | | | TB0219G | 6 | 2 | | ALL |
| B-A | | | | 0-0 | 27-62-11 | S00374 | | NC | | | | | TB0215G | 15 | 2 | | ALL |
| B-B | | | | 0-0 | 27-62-11 | S00374 | | C | | | | | TB0215F | A014 | 2 | | ALL |

WIRE LIST

D280T132

91-21-11

Section W5150

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|---------------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5150 | 286T5150 | | | P10 QUADRANT STAND (continued) | | | | | | | | | | | |
| B-C | | | | | 0-0 | 27-62-11 | S00374 | | NO | | TB0215F | C014 | 2 | | ALL |
| C-A | | | | | 0-0 | 27-51-31 | M00603 | | RWH | | TB0215F | A001 | 2 | | ALL |
| C-B | | | | | 0-0 | 27-51-31 | M00603 | | BKW | | TB0215F | C001 | 2 | | ALL |
| C-C | | | | | 0-0 | 27-51-31 | M00603 | | ORG | | TB0215F | A002 | 2 | | ALL |
| C-D | | | | | 0-0 | 27-51-31 | M00603 | | YEL | | TB0215F | C002 | 2 | | ALL |
| C-E | | | | | 0-0 | 27-51-31 | M00603 | | BLU | | TB0215G | | 3 | 2 | ALL |
| C-F | | | | | 0-0 | 27-51-31 | M00603 | | GRN | | GD00619 | S.. | | E | ALL |
| D-A | | | | | 0-0 | 27-58-31 | M00604 | | RWH | | TB0215F | A004 | 2 | | ALL |
| D-B | | | | | 0-0 | 27-58-31 | M00604 | | BKW | | TB0215F | C004 | 2 | | ALL |
| D-C | | | | | 0-0 | 27-58-31 | M00604 | | ORG | | TB0215F | A005 | 2 | | ALL |
| D-D | | | | | 0-0 | 27-58-31 | M00604 | | YEL | | TB0215F | C005 | 2 | | ALL |
| D-E | | | | | 0-0 | 27-58-31 | M00604 | | BLU | | TB0215G | | 6 | 2 | ALL |
| D-F | | | | | 0-0 | 27-58-31 | M00604 | | GRN | | GD00621 | S.. | | 2 | ALL |
| E-A | | | | | 0-0 | 27-41-11 | S00538 | | C | | TB0217G | | 1 | 2 | 150-154 |
| E-B | | | | | 0-0 | 27-41-11 | S00538 | | NO | | GD00639 | D.. | | 2 | 150-154 |
| F-A | | | | | 0-0 | 33-13-18 | L00576 | | BLK | | TB0217G | | 2 | 2 | ALL |
| F-B | | | | | 0-0 | 33-13-18 | L00576 | | WHT | | GD00609 | A.. | | 2 | ALL |
| G-A | | | | | 0-0 | 33-13-18 | L00496 | | BLK | | TB0217H | | 4 | 2 | ALL |
| G-B | | | | | 0-0 | 33-13-18 | L00496 | | WHT | | GD00609 | A.. | | 2 | 050-099, 150-155, 162-165, 275-276 |
| G-B | | | | | 0-0 | 33-13-18 | L00496 | | WHT | | TB0217H | | 9 | 2 | 156-157, 166-199, 277-299 |
| H-A | | | | | 0-0 | 33-13-18 | L00604 | | BLK | | TB0217H | | 4 | 2 | ALL |
| H-B | | | | | 0-0 | 33-13-18 | L00604 | | WHT | | GD00609 | A.. | | 2 | 050-099, 150-155, 162-165, 275-276 |
| H-B | | | | | 0-0 | 33-13-18 | L00604 | | WHT | | TB0217H | | 9 | 2 | 156-157, 166-199, 277-299 |
| K-A | | | | | 0-0 | 33-13-18 | L00577 | | BLK | | TB0217G | | 3 | 2 | ALL |
| K-B | | | | | 0-0 | 33-13-18 | L00577 | | WHT | | GD00609 | A.. | | 2 | ALL |
| L-A | | | | | 0-0 | 32-42-12 | S00493 | | A-B | | TB0219H | | 9 | 2 | ALL |
| L-B | | | | | 0-0 | 32-42-12 | S00493 | | A-K | | TB0219G | | 8 | 2 | ALL |
| L-C | | | | | 0-0 | 32-42-12 | S00493 | | A-R | | TB0219 | CAP | | Y | ALL |
| L-D | | | | | 0-0 | 31-51-41 | S00493 | | B-B | | GD00601 | D.. | | 2 | ALL |
| L-E | | | | | 0-0 | 31-51-41 | S00493 | | B-K | | TB0219F | A007 | | 2 | ALL |
| L-F | | | | | 0-0 | 29-11-32 | S00493 | | B-R | | TB0219F | C007 | | 2 | ALL |
| M-A | | | | | 0-0 | 27-61-15 | TS0035 | | RED | | D04131P | | 1 | | ALL |
| M-B | | | | | 0-0 | 27-61-15 | TS0035 | | BLK | | D04131P | | 2 | | ALL |
| M-C | | | | | 0-0 | 27-61-15 | TS0035 | | YEL | | D04131P | | 3 | | ALL |
| M-D | | | | | 0-0 | 27-61-15 | TS0035 | | ORG | | D04131P | | 4 | | ALL |

WIRE LIST

D280T132

91-21-11
Section W5150
Page 6
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|--|-----------------|----|----|-------------|-------|---------------------------------------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5150 | | 286T5150 | | | | | P10 QUADRANT STAND (continued) | | | | | | | | | |
| M-E | | | | | | 0-0 | 27-61-15 | TS0035 | | BLU | | D04131P | | 5 | | ALL |
| M-F | | | | | | 0-0 | 27-61-15 | TS0035 | | PUR | | D04131P | | 6 | | ALL |
| N-A | | | | | | 0-0 | 27-61-17 | TS0035 | | RED | | D04137P | | 1 | | ALL |
| N-B | | | | | | 0-0 | 27-61-17 | TS0035 | | BLK | | D04137P | | 2 | | ALL |
| N-C | | | | | | 0-0 | 27-61-17 | TS0035 | | YEL | | D04137P | | 3 | | ALL |
| N-D | | | | | | 0-0 | 27-61-17 | TS0035 | | ORG | | D04137P | | 4 | | ALL |
| N-E | | | | | | 0-0 | 27-61-17 | TS0035 | | BLU | | D04137P | | 5 | | ALL |
| N-F | | | | | | 0-0 | 27-61-17 | TS0035 | | PUR | | D04137P | | 6 | | ALL |
| P-A | | | | | | 0-0 | 27-61-14 | TS0036 | | RED | | D04133P | | 1 | | ALL |
| P-B | | | | | | 0-0 | 27-61-14 | TS0036 | | BLK | | D04133P | | 2 | | ALL |
| P-C | | | | | | 0-0 | 27-61-14 | TS0036 | | YEL | | D04133P | | 3 | | ALL |
| P-D | | | | | | 0-0 | 27-61-14 | TS0036 | | ORG | | D04133P | | 4 | | ALL |
| P-E | | | | | | 0-0 | 27-61-14 | TS0036 | | BLU | | D04133P | | 5 | | ALL |
| P-F | | | | | | 0-0 | 27-61-14 | TS0036 | | PUR | | D04133P | | 6 | | ALL |
| R-A | | | | | | 0-0 | 27-61-13 | TS0036 | | RED | | D04139P | | 1 | | ALL |
| R-B | | | | | | 0-0 | 27-61-13 | TS0036 | | BLK | | D04139P | | 2 | | ALL |
| R-C | | | | | | 0-0 | 27-61-13 | TS0036 | | YEL | | D04139P | | 3 | | ALL |
| R-D | | | | | | 0-0 | 27-61-13 | TS0036 | | ORG | | D04139P | | 4 | | ALL |
| R-E | | | | | | 0-0 | 27-61-13 | TS0036 | | BLU | | D04139P | | 5 | | ALL |
| R-F | | | | | | 0-0 | 27-61-13 | TS0036 | | PUR | | D04139P | | 6 | | ALL |
| S-A | | | | | | 0-0 | 27-61-16 | TS0037 | | RED | | D04135P | | 1 | | ALL |
| S-B | | | | | | 0-0 | 27-61-16 | TS0037 | | BLK | | D04135P | | 2 | | ALL |
| S-C | | | | | | 0-0 | 27-61-16 | TS0037 | | YEL | | D04135P | | 3 | | ALL |
| S-D | | | | | | 0-0 | 27-61-16 | TS0037 | | ORG | | D04135P | | 4 | | ALL |
| S-E | | | | | | 0-0 | 27-61-16 | TS0037 | | BLU | | D04135P | | 5 | | ALL |
| S-F | | | | | | 0-0 | 27-61-16 | TS0037 | | PUR | | D04135P | | 6 | | ALL |
| T-A | | | | | | 0-0 | 27-61-18 | TS0037 | | RED | | D04141P | | 1 | | ALL |
| T-B | | | | | | 0-0 | 27-61-18 | TS0037 | | BLK | | D04141P | | 2 | | ALL |
| T-C | | | | | | 0-0 | 27-61-18 | TS0037 | | YEL | | D04141P | | 3 | | ALL |
| T-D | | | | | | 0-0 | 27-61-18 | TS0037 | | ORG | | D04141P | | 4 | | ALL |
| T-E | | | | | | 0-0 | 27-61-18 | TS0037 | | BLU | | D04141P | | 5 | | ALL |
| T-F | | | | | | 0-0 | 27-61-18 | TS0037 | | PUR | | D04141P | | 6 | | ALL |
| V-A | | | | | | 0-0 | 31-31-15 | S00575 | | NO | | TB0215F | C017 | 2 | | 150-154 |
| V-B | | | | | | 0-0 | 31-31-15 | S00575 | | COM | | GD00639 | D.. | 2 | | 150-154 |

WIRE LIST

D280T132

91-21-11

Section W5150

Page 7 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9000 | 286T9000 | | | P8 TO PURSER STATION / VIDEO | | | | | | | | | | | |
| 900 | 20 | | PA | | 5-0 | 33-26-21 | D13444P | 51 | | | D06045P | 20 | | | 151-152 |
| W9002 | 286T9002 | | | CUSTOMER WBA - VIDEO PROJECTION DISTRIBUTION | | | | | | | | | | | |
| 002 | 20 | | PA | | 8-0 | 23-32-13 | D09004 | | K | | SM00001 | | S | | 150, 153-157 |
| 003 | 20 | | PA | | 8-0 | 23-32-13 | D09004 | | L | | SM00002 | | S | | 150, 153-157 |
| 004 | 20 | | PA | | 8-0 | 23-32-13 | D09004 | | J | | SM00003 | | S | | 150, 153-157 |
| 005 | 22 | | PA | | 8-0 | 23-32-13 | D09004 | | H | | SM00004 | | S | | 150, 153-157 |
| 006 | 22 | | PA | | 8-0 | 23-32-13 | D09004 | | F | | SM00005 | | S | | 150, 153-157 |
| 007 | 22 | | PA | | 8-0 | 23-32-13 | D09004 | | E | | SM00006 | | S | | 150, 153-157 |
| 008 | 20 | | PA | | 8-0 | 23-32-13 | D09004 | | G | | SM00007 | | S | | 150, 153-157 |
| 009 | 20 | | PA | | 8-0 | 23-32-13 | D09004 | | M | | SM00008 | | S | | 150, 153-157 |
| 012 | 20 | | PA | | 10-0 | 23-32-13 | D09002P | | 1 | | SM00001 | | S | | 150, 153-157 |
| 013 | 20 | | PA | | 10-0 | 23-32-13 | D09002P | | 4 | | SM00002 | | S | | 150, 153-157 |
| 014 | 20 | | PA | | 10-0 | 23-32-13 | D09002P | | 5 | | SM00003 | | S | | 150, 153-157 |
| 015 | 22 | | PA | | 10-0 | 23-32-13 | D09002P | | 6 | | SM00004 | | S | | 150, 153-157 |
| 016 | 22 | | PA | | 10-0 | 23-32-13 | D09002P | | 8 | | SM00005 | | S | | 150, 153-157 |
| 017 | 22 | | PA | | 10-0 | 23-32-13 | D09002P | | 7 | | SM00006 | | S | | 150, 153-157 |
| 018 | 20 | | PA | | 10-0 | 23-32-13 | D09002P | | 3 | | SM00007 | | S | | 150, 153-157 |
| 019 | 20 | | PA | | 10-0 | 23-32-13 | D09002P | | 2 | | SM00008 | | S | | 150, 153-157 |
| 01CO | | | | A | 0-0 | 23-32-13 | D09006 | | = C1 | | D09002P | C15 | | | 150, 153-157 |
| 01CX | | | 5X | A | 18-0 | 23-32-13 | D09006 | | = A1 | | D09002P | 15 | | | 150, 153-157 |
| 022 | 20 | | PA | | 21-0 | 23-32-13 | D09001P | | 1 | | SM00001 | | S | | 150, 153-157 |
| 023 | 20 | | PA | | 21-0 | 23-32-13 | D09001P | | 4 | | SM00002 | | S | | 150, 153-157 |
| 024 | 20 | | PA | | 21-0 | 23-32-13 | D09001P | | 5 | | SM00003 | | S | | 150, 153-157 |
| 025 | 22 | | PA | | 21-0 | 23-32-13 | D09001P | | 6 | | SM00004 | | S | | 150, 153-157 |
| 026 | 22 | | PA | | 21-0 | 23-32-13 | D09001P | | 8 | | SM00005 | | S | | 150, 153-157 |
| 027 | 22 | | PA | | 21-0 | 23-32-13 | D09001P | | 7 | | SM00006 | | S | | 150, 153-157 |
| 028 | 20 | | PA | | 21-0 | 23-32-13 | D09001P | | 3 | | SM00007 | | S | | 150, 153-157 |
| 029 | 20 | | PA | | 21-0 | 23-32-13 | D09001P | | 2 | | SM00008 | | S | | 150, 153-157 |
| 02CO | | | | B | 0-0 | 23-32-13 | D09001P | | C15 | | D09002P | C19 | | | 150, 153-157 |
| 02CX | | | 5X | B | 21-0 | 23-32-13 | D09001P | | 15 | | D09002P | 19 | | | 150, 153-157 |
| W9003 | 286T9003 | | | CUSTOMER WBA - VIDEO PROJECTION DISTRIBUTION | | | | | | | | | | | |
| 002 | 20 | | PA | | 4-0 | 23-32-13 | D09007 | | 1 | | D09001J | 1 | | | 150, 153-157 |
| 003 | 20 | | PA | | 4-0 | 23-32-13 | D09007 | | 4 | | D09001J | 4 | | | 150, 153-157 |
| 004 | 20 | | PA | | 4-0 | 23-32-13 | D09007 | | 5 | | D09001J | 5 | | | 150, 153-157 |
| 005 | 22 | | PA | | 4-0 | 23-32-13 | D09007 | | 6 | | D09001J | 6 | | | 150, 153-157 |
| 006 | 22 | | PA | | 4-0 | 23-32-13 | D09007 | | 8 | | D09001J | 8 | | | 150, 153-157 |
| 007 | 22 | | PA | | 4-0 | 23-32-13 | D09007 | | 7 | | D09001J | 7 | | | 150, 153-157 |

WIRE LIST

D280T132

91-21-11

Section W9000

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|-------|---------|------|--------|---|--------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W9003 | 286T9003 | | | CUSTOMER WBA - VIDEO PROJECTION DISTRIBUTION (continued) | | | | | | | | | | | | |
| 008 | 20 | PA | | 4-0 | 23-32-13 | D09007 | | 3 | | | | D09001J | | 3 | | 150, 153-157 |
| 009 | 20 | PA | | 4-0 | 23-32-13 | D09007 | | 2 | | | | D09001J | | 2 | | 150, 153-157 |
| 010 | 22 | PA | | 10-0 | 33-22-21 | S09001 | | = 1 | C | | | D09001J | | 16 | | 150, 153-199 |
| 011 | 22 | PA | | 10-0 | 33-22-21 | L09001 | | = G | C | | | D09001J | | 17 | | 150, 153-199 |
| 012 | 22 | PA | | 10-0 | 33-22-21 | L09001 | | = P | C | | | S09001 | | = 2 | C | 150, 153-199 |
| 01CO | | | A | 0-0 | 23-32-13 | D09007 | | = C1 | | | | D09001J | | C15 | | 150, 153-157 |
| 01CX | | 5X | A | 4-0 | 23-32-13 | D09007 | | = A1 | | | | D09001J | | 15 | | 150, 153-157 |
| W9004 | 286T9004 | | | CUSTOMER WBA - VIDEO PROJECTION DISTRIBUTION | | | | | | | | | | | | |
| 002 | 20 | PA | | 4-0 | 23-32-13 | D09008 | | 1 | | | | D09002J | | 1 | | 150, 153-157 |
| 003 | 20 | PA | | 4-0 | 23-32-13 | D09008 | | 4 | | | | D09002J | | 4 | | 150, 153-157 |
| 004 | 20 | PA | | 4-0 | 23-32-13 | D09008 | | 5 | | | | D09002J | | 5 | | 150, 153-157 |
| 005 | 22 | PA | | 4-0 | 23-32-13 | D09008 | | 6 | | | | D09002J | | 6 | | 150, 153-157 |
| 006 | 22 | PA | | 4-0 | 23-32-13 | D09008 | | 8 | | | | D09002J | | 8 | | 150, 153-157 |
| 007 | 22 | PA | | 4-0 | 23-32-13 | D09008 | | 7 | | | | D09002J | | 7 | | 150, 153-157 |
| 008 | 20 | PA | | 4-0 | 23-32-13 | D09008 | | 3 | | | | D09002J | | 3 | | 150, 153-157 |
| 009 | 20 | PA | | 4-0 | 23-32-13 | D09008 | | 2 | | | | D09002J | | 2 | | 150, 153-157 |
| 010 | 22 | PA | | 10-0 | 33-22-21 | D09002J | | 16 | | | | SMZ0001 | | | S | 150, 153-157 |
| 011 | 22 | PA | | 10-0 | 33-22-21 | D09002J | | 17 | | | | SMZ0002 | | | S | 150, 153-157 |
| 012 | 22 | PA | | 10-0 | 33-22-21 | S09002 | | = 1 | C | | | SMZ0001 | | | S | 150, 153-157 |
| 013 | 22 | PA | | 10-0 | 33-22-21 | L09002 | | = G | C | | | SMZ0002 | | | S | 150, 153-157 |
| 014 | 22 | PA | | 10-0 | 33-22-21 | S09002 | | = 2 | C | | | L09002 | | = P | C | 150, 153-157 |
| 015 | 22 | PA | | 10-0 | 33-22-21 | L09003 | | = G | C | | | SMZ0002 | | | S | 150, 153-157 |
| 016 | 22 | PA | | 10-0 | 33-22-21 | SMZ0001 | | | S | | | S09003 | | = 1 | C | 150, 153-157 |
| 017 | 22 | PA | | 10-0 | 33-22-21 | S09003 | | = 2 | C | | | L09003 | | = P | C | 150, 153-157 |
| 01CO | | | A | 0-0 | 23-32-13 | D09008 | | = C1 | | | | D09002J | | C15 | | 150, 153-157 |
| 01CX | | 5X | A | 4-0 | 23-32-13 | D09008 | | = A1 | | | | D09002J | | 15 | | 150, 153-157 |
| 02CO | | | B | 0-0 | 23-32-13 | D09010 | | = C1 | | | | D09002J | | C19 | | 150, 153-157 |
| 02CX | | 5X | B | 4-0 | 23-32-13 | D09010 | | = A1 | | | | D09002J | | 19 | | 150, 153-157 |
| W9005 | 286T9005 | | | CUSTOMER WBA - P19 TO VCC CLOSET STA 448 | | | | | | | | | | | | |
| 001 | 22 | PA | | 19-8 | 33-22-21 | D09001P | | 16 | | | | D05110P | | 28 | | 150, 153-157 |
| 001 | 22 | PA | | 19-9 | 33-22-21 | D09001P | | 16 | | | | D05110P | | 28 | | 162-199 |
| 002 | 22 | PA | | 13-2 | 33-22-21 | D09001P | | 17 | | | | GD01022 | | A.. | E | 150, 153-157 |
| 002 | 20 | PA | | 10-0 | 23-32-13 | D09015 | | K | | | | D09017 | | 1 | | 162-199 |
| 003 | 20 | PA | | 10-0 | 23-32-13 | D09015 | | L | | | | D09017 | | 4 | | 162-199 |
| 004 | 20 | PA | | 10-0 | 23-32-13 | D09015 | | J | | | | D09017 | | 5 | | 162-199 |
| 005 | 22 | PA | | 10-0 | 23-32-13 | D09015 | | H | | | | D09017 | | 6 | | 162-199 |
| 006 | 22 | PA | | 10-0 | 23-32-13 | D09015 | | F | | | | D09017 | | 8 | | 162-199 |

WIRE LIST

D280T132

91-21-11

Section W9000

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|---|----|-----|-------------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9005 | 286T9005 | CUSTOMER WBA - P19 TO VCC CLOSET STA 448 (continued) | | | | | | | | | | | | | |
| 007 | 22 | | PA | | 10-0 | 23-32-13 | D09015 | | E | | D09017 | | 7 | | 162-199 |
| 008 | 20 | | PA | | 10-0 | 23-32-13 | D09015 | | G | | D09017 | | 3 | | 162-199 |
| 009 | 20 | | PA | | 10-0 | 23-32-13 | D09015 | | M | | D09017 | | 2 | | 162-199 |
| 01CO | | | | A | 0-0 | 23-32-13 | D09016 | | =C1 | | D09018 | | =C1 | | 162-199 |
| 01CX | | 5X | | A | 10-0 | 23-32-13 | D09016 | | =A1 | | D09018 | | =A1 | | 162-199 |
| A02 | 22 | | PA | | 13-2 | 33-22-21 | D09001P | | 17 | | GD01022 | | A.. | E | 162-199 |
| W9006 | 286T9006 | CUSTOMER WBA - P19 TO COATROOM STA 448 | | | | | | | | | | | | | |
| 001 | 22 | | PA | | 29-7 | 33-22-21 | D09002P | | 16 | | D05114P | | 26 | | 150, 153-157 |
| 001B | 24 | | PW | A | 10-0 | 23-31-11 | D02535 | | 3 | | D00837P | | 9 | | 050-099 |
| 001R | 24 | | PW | A | 0-0 | 23-31-11 | D02535 | | 4 | | D00837P | | 8 | | 050-099 |
| 001Z | | | | A | 0-0 | 23-31-11 | D02535 | | DED | | D00837P | | 10 | | 050-099 |
| 002 | 24 | | PK | | 10-0 | 23-31-11 | D02535 | | 2 | | D00837P | | 6 | | 050-099 |
| 002 | 22 | | PA | | 13-2 | 33-22-21 | D09002P | | 17 | | GD00938 | | A.. | 2 | 150, 153-157 |
| 003 | 24 | | PK | | 10-0 | 23-31-11 | D02535 | | 1 | | D00837P | | 7 | | 050-099 |
| 004 | 24 | | PK | | 10-0 | 23-31-12 | S09001 | | 1 | E | D00837P | | 4 | | 050-099 |
| 005 | 24 | | PK | | 10-0 | 23-31-12 | S09001 | | 2 | E | D00837P | | 5 | | 050-099 |
| 301B | 24 | | PM | B | 10-0 | 23-31-12 | S09001 | | CCV | | D00837P | | 3 | | 050-099 |
| 301R | 24 | | PM | B | 0-0 | 23-31-12 | S09001 | | CV | | D00837P | | 1 | | 050-099 |
| 301Y | 24 | | PM | B | 0-0 | 23-31-12 | S09001 | | CCV | | D00837P | | 2 | | 050-099 |
| W9007 | 286T9007 | IN SEAT POWER OUTLETS FORWARD CABIN, E002-06 | | | | | | | | | | | | | |
| 001 | 16 | | PA | | 10-0 | 25-25-23 | C09033 | | A02 | D | D09048 | | A | | 150, 153-199 |
| 002 | 16 | | PA | | 10-0 | 25-25-23 | C09033 | | B02 | D | D09048 | | B | | 150, 153-199 |
| 003 | 16 | | PA | | 10-0 | 25-25-23 | C09033 | | C02 | D | D09048 | | C | | 150, 153-199 |
| 004 | 16 | | PA | | 3-0 | 25-25-23 | GD09001 | | D.. | E | D09048 | | D | | 150, 153-199 |
| W9008 | 286T9008 | IN SEAT POWER OUTLETS FORWARD CABIN, E002-06 | | | | | | | | | | | | | |
| 001 | 06 | | PA | | 10-0 | 25-25-23 | D09000 | | 1 | | C09034 | | 1 | D | 150, 153-199 |
| 002 | 06 | | PA | | 10-0 | 25-25-23 | D09000 | | 2 | | TB9001 | | 1 | E | 150, 153-199 |
| 003 | 16 | | PA | | 10-0 | 25-25-23 | C09034 | | 2 | D | D09055P | | 1 | | 150, 153-199 |
| 004 | 16 | | PA | | 10-0 | 25-25-23 | D09055P | | 2 | | TB9001 | | 2 | E | 150, 153-199 |
| 005 | 16 | | PA | | 10-0 | 25-25-23 | C09035 | | 2 | D | D09055P | | 3 | | 150, 153-199 |
| 006 | 16 | | PA | | 10-0 | 25-25-23 | TB9001 | | 2 | E | D09055P | | 4 | | 150, 153-199 |
| 007 | 16 | | PA | | 10-0 | 25-25-23 | C09036 | | 2 | D | D09055P | | 5 | | 150, 153-199 |
| 008 | 16 | | PA | | 10-0 | 25-25-23 | TB9001 | | 3 | E | D09055P | | 6 | | 150, 153-199 |
| 009 | 16 | | PA | | 10-0 | 25-25-24 | C09037 | | 2 | D | D09055P | | 7 | | 150, 153-199 |
| 010 | 16 | | PA | | 10-0 | 25-25-24 | D09055P | | 8 | | TB9001 | | 3 | E | 150, 153-199 |

WIRE LIST

D280T132

91-21-11

Section W9000

Page 3

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|-------|------|---------|--------|----|-------------|--|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W9008 | 286T9008 | | | IN SEAT POWER OUTLETS FORWARD CABIN, E002-06 (continued) | | | | | | | | | | | | | | |
| 011 | 16 | | PA | 10-0 | 25-25-24 | C09038 | | 2 | D | | | | D09055P | | 9 | | | 150, 153-199 |
| 012 | 16 | | PA | 10-0 | 25-25-24 | TB9001 | | 4 | E | | | | D09055P | | 10 | | | 150, 153-199 |
| 013 | 16 | | PA | 10-0 | 25-25-24 | C09039 | | 2 | D | | | | D09055P | | 11 | | | 150, 153-199 |
| 014 | 16 | | PA | 10-0 | 25-25-24 | TB9001 | | 4 | E | | | | D09055P | | 12 | | | 150, 153-199 |
| 015 | 16 | | PA | 10-0 | 25-25-23 | C09034 | | 2 | D | | | | D09055P | | 13 | | | 150, 153-199 |
| 016 | 16 | | PA | 10-0 | 25-25-24 | TB9001 | | 2 | E | | | | D09055P | | 14 | | | 150, 153-199 |
| 017 | 16 | | PA | 3-0 | 25-25-23 | TB9001 | | 1 | E | | | | GD09002 | D.. | E | | | 150, 153-199 |
| ZZA01 | 03 | | ZB | 0-0 | 25-25-23 | C09034 | | 1 | D | | | | C09036 | | 1 | D | | 150, 153-199 |
| ZZA02 | 00 | | ZB | 0-0 | 25-25-23 | C09034 | | 1 | D | | | | C09035 | | 1 | D | | 150, 153-199 |
| ZZA03 | 00 | | ZB | 0-0 | 25-25-23 | C09035 | | 1 | D | | | | C09036 | | 1 | D | | 150, 153-199 |
| ZZA04 | 04 | | ZB | 0-0 | 25-25-23 | TB9001 | | 1 | E | | | | TB9001 | | 4 | E | | 150, 153-199 |
| ZZA05 | 03 | | ZB | 0-0 | 25-25-24 | C09037 | | 1 | D | | | | C09039 | | 1 | D | | 150, 153-199 |
| ZZA06 | 00 | | ZB | 0-0 | 25-25-24 | C09037 | | 1 | D | | | | C09038 | | 1 | D | | 150, 153-199 |
| ZZA07 | 00 | | ZB | 0-0 | 25-25-24 | C09038 | | 1 | D | | | | C09039 | | 1 | D | | 150, 153-199 |
| ZZA08 | 04 | | ZB | 0-0 | 25-25-24 | TB9001 | | 1 | E | | | | TB9001 | | 4 | E | | 150, 153-199 |
| W9009 | 286T9009 | | | IN SEAT POWER OUTLETS FORWARD CABIN, E002-06 | | | | | | | | | | | | | | |
| 001 | 16 | | PA | 10-0 | 25-25-23 | D09055J | | 1 | | | | | D09049J | | 2 | | | 150, 153-199 |
| 002 | 16 | | PA | 10-0 | 25-25-23 | D09055J | | 2 | | | | | D09049J | | 1 | | | 150, 153-199 |
| 003 | 16 | | PA | 10-0 | 25-25-23 | D09055J | | 3 | | | | | D09050J | | 2 | | | 150, 153-199 |
| 004 | 16 | | PA | 10-0 | 25-25-23 | D09055J | | 4 | | | | | D09050J | | 1 | | | 150, 153-199 |
| 005 | 16 | | PA | 10-0 | 25-25-23 | D09055J | | 5 | | | | | D09051J | | 2 | | | 150, 153-199 |
| 006 | 16 | | PA | 10-0 | 25-25-23 | D09055J | | 6 | | | | | D09051J | | 1 | | | 150, 153-199 |
| 007 | 16 | | PA | 10-0 | 25-25-24 | D09055J | | 7 | | | | | D09052J | | 2 | | | 150, 153-199 |
| 008 | 16 | | PA | 10-0 | 25-25-24 | D09055J | | 8 | | | | | D09052J | | 1 | | | 150, 153-199 |
| 009 | 16 | | PA | 10-0 | 25-25-24 | D09055J | | 9 | | | | | D09053J | | 2 | | | 150, 153-199 |
| 010 | 16 | | PA | 10-0 | 25-25-24 | D09055J | | 10 | | | | | D09053J | | 1 | | | 150, 153-199 |
| 011 | 16 | | PA | 10-0 | 25-25-24 | D09055J | | 11 | | | | | D09054J | | 2 | | | 150, 153-199 |
| 012 | 16 | | PA | 10-0 | 25-25-24 | D09055J | | 12 | | | | | D09054J | | 1 | | | 150, 153-199 |
| 013 | 16 | | PA | 10-0 | 25-25-23 | D09055J | | 13 | | | | | D09047J | | 2 | | | 150, 153-199 |
| 014 | 16 | | PA | 10-0 | 25-25-24 | D09055J | | 14 | | | | | D09047J | | 1 | | | 150, 153-199 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9011 | 286T9011 | | | SATCOM - E9-1 TO P11 PNL (CUSTOMER) | | | | | | | | | | | |
| 901 | 16 | | PA | | 152-0 | 23-25-11 | D04273P | 36 | FL | | D06149J | 21 | | | 150, 153-155, 162-165 |
| 902 | 20 | | PA | | 150-0 | 23-25-13 | D04273P | 22 | | | D06149J | 39 | | | 150, 153-199 |
| 903 | 16 | | PA | | 152-0 | 23-25-11 | D04273P | 12 | FL | | D06149J | 23 | | | 150, 153-199 |
| W9012 | 286T9012 | | | SATCOM - E9-1 TO P9 PNL (CUSTOMER) | | | | | | | | | | | |
| 201B | 22 | | PR | IA | 140-0 | 23-25-13 | D00467 | 12 | | | D06155J | 5 | | | 150, 153-155, 162-165 |
| 201R | 22 | | PR | IA | 0-0 | 23-25-13 | D00467 | 11 | | | D06155J | 4 | | | 150, 153-155, 162-165 |
| 201Z | | | | IA | 0-0 | 23-25-13 | GD00235 | S.. | 2 | | D06155J | 24 | | | 150, 153-155, 162-165 |
| 208B | 22 | | PR | IH | 140-0 | 23-25-13 | D00465 | 12 | | | D06149J | 24 | | | 150, 153-155, 162-165 |
| 208R | 22 | | PR | IH | 0-0 | 23-25-13 | D00465 | 11 | | | D06149J | 22 | | | 150, 153-155, 162-165 |
| 208Z | | | | IH | 0-0 | 23-25-13 | GD00208 | S.. | 2 | | D06149J | 20 | | | 150, 153-155, 162-165 |
| W9013 | 286T9013 | | | SATCOM - E9-1 TO P61 PNL (CUSTOMER) | | | | | | | | | | | |
| 209 | 22 | | PA | | 150-0 | 23-25-13 | D06225P | 19 | | | D06149J | 35 | | | 150, 153-199 |
| 210B | 22 | | PR | IJ | 150-0 | 23-25-13 | D06225P | 17 | | | D06149J | 37 | | | 150, 153-199 |
| 210R | 22 | | PR | IJ | 0-0 | 23-25-13 | D06225P | 16 | | | D06149J | 36 | | | 150, 153-199 |
| 210Z | | | | IJ | 0-0 | 23-25-13 | D06225P | 18 | | | D06149J | 38 | | | 150, 153-199 |
| 925 | 22 | | PA | | 150-0 | 23-25-13 | D96102P | M | | | D96101J | 13 | | | 150, 153-199 |
| 926 | 22 | | PA | | 150-0 | 23-25-13 | D96102P | J | | | D96101J | 14 | | | 150, 153-199 |
| 927 | 22 | | PA | | 150-0 | 23-25-13 | D96102P | K | | | D96101J | 15 | | | 150, 153-199 |
| 928 | 22 | | PA | | 150-0 | 23-25-13 | D96102P | G | | | D96101J | 16 | | | 150, 153-199 |
| 929 | 22 | | PA | | 150-0 | 23-25-13 | D96102P | H | | | D96101J | 17 | | | 150, 153-199 |
| 930 | 22 | | PA | | 150-0 | 23-25-13 | D96102P | E | | | D96101J | 18 | | | 150, 153-199 |
| 931 | 22 | | PA | | 150-0 | 23-25-13 | D96102P | C | | | D96101J | 19 | | | 150, 153-199 |
| 932 | 22 | | PA | | 150-0 | 23-25-13 | D96102P | A | | | D96101J | 20 | | | 150, 153-199 |
| 933 | 22 | | PA | | 150-0 | 23-25-13 | D96102P | L | | | D96101J | 21 | | | 150, 153-199 |
| 934B | 22 | | PR | HX | 150-0 | 23-25-13 | D96102P | V | | | D96101J | 23 | | | 150, 153-199 |
| 934R | 22 | | PR | HX | 0-0 | 23-25-13 | D96102P | W | | | D96101J | 22 | | | 150, 153-199 |
| 934Z | | | | HX | 0-0 | 23-25-13 | D96102P | REF | | HX | D96101J | REF | | HW | 150, 153-199 |
| 936B | 22 | | PR | HW | 150-0 | 23-25-13 | D96102P | T | | | D96101J | 25 | | | 150, 153-199 |
| 936R | 22 | | PR | HW | 0-0 | 23-25-13 | D96102P | U | | | D96101J | 24 | | | 150, 153-199 |
| 936Z | | | | HW | 0-0 | 23-25-13 | D96102P | REF | | HX | D96101J | REF | | HW | 150, 153-199 |
| 938 | 20 | | PA | | 150-0 | 23-25-13 | D96102P | C- | | | D96101J | 26 | | | 150, 153-199 |
| 939 | 20 | | PA | | 150-0 | 23-25-13 | D96102P | A- | | | D96101J | 27 | | | 150, 153-199 |
| 940 | 20 | | PA | | 150-0 | 23-25-13 | D96102P | B- | | | D96101J | 28 | | | 150, 153-199 |
| FRW | | | | | 0-0 | 23-25-13 | D96101J | 29 | | | D96101J | REF | | HW | 150, 153-199 |
| FRX | | | | | 0-0 | 23-25-13 | D96102P | REF | | HX | D96102P | X | | | 150, 153-199 |

WIRE LIST

D280T132

91-21-11

Section W9010

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|---------|-------|------|------|-----------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9014 | 286T9014 | | | SATCOM - E9-1 TO E1-6 PNL (CUSTOMER) | | | | | | | | | | | |
| 205B | 22 | PR | IE | 130-0 | 23-25-13 | D04769J | 44 | | | D06155J | 17 | | | 150, 153-155, 162-165 | |
| 205R | 22 | PR | IE | 0-0 | 23-25-13 | D04769J | 43 | | | D06155J | 16 | | | 150, 153-155, 162-165 | |
| 205Z | | | IE | 0-0 | 23-25-13 | D04769J | 42 | | | D06155J | 15 | | | 150, 153-155, 162-165 | |
| 207B | 22 | PR | IG | 130-0 | 23-25-13 | D04719J | 45 | | | D06149J | 19 | | | 150, 153-155, 162-165 | |
| 207R | 22 | PR | IG | 0-0 | 23-25-13 | D04719J | 44 | | | D06149J | 18 | | | 150, 153-155, 162-165 | |
| 207Z | | | IG | 0-0 | 23-25-13 | D04719J | 46 | | | D06149J | 17 | | | 150, 153-155, 162-165 | |
| W9015 | 286T9015 | | | SATCOM - E9-1 TO E2-2 SHELF (CUSTOMER) | | | | | | | | | | | |
| 215B | 22 | PR | IO | 112-2 | 23-25-13 | D04229J | 23 | | | D06165J | 40 | | | 150, 153-199 | |
| 215R | 22 | PR | IO | 0-0 | 23-25-13 | D04229J | 22 | | | D06165J | 39 | | | 150, 153-199 | |
| 215Z | | | IO | 0-0 | 23-25-13 | D04229J | 24 | | | D06165J | 41 | | | 150, 153-199 | |
| W9019 | 286T9019 | | | COAX-SATCOM, E9 TO E10 | | | | | | | | | | | |
| 003 | 20 | PA | | 1-8 | 23-25-16 | D06165J | 14 | | | D06167P | 9 | | | 150, 153-155, 162-165 | |
| 004 | 20 | PA | | 1-8 | 23-25-16 | D06167P | 10 | | | GD01906 | A.. | 2 | | 150, 153-155, 162-165 | |
| 005 | 20 | PA | | 1-8 | 23-25-16 | D06167P | 11 | | | GD01906 | S.. | 2 | | 150, 153-155, 162-165 | |
| 205 | 20 | UA | | 1-6 | 23-25-16 | D06167P | REF | | IE | GD01906 | S.. | 2 | | 150, 153-155, 162-165 | |
| 205B | 22 | PR | IE | 55-10 | 23-25-16 | D06165J | 18 | | | D06167P | 4 | | | 150, 153-155, 162-165 | |
| 205R | 22 | PR | IE | 0-0 | 23-25-16 | D06165J | 17 | | | D06167P | 5 | | | 150, 153-155, 162-165 | |
| 205Z | | | IE | 0-0 | 23-25-16 | D06165J | 19 | | | D06167P | REF | | IE | 150, 153-155, 162-165 | |
| 206 | 20 | UA | | 1-6 | 23-25-16 | D06167P | REF | | IF | GD01906 | S.. | 2 | | 150, 153-155, 162-165 | |
| 206B | 22 | PR | IF | 55-10 | 23-25-16 | D06165J | 21 | | | D06167P | 1 | | | 150, 153-155, 162-165 | |
| 206R | 22 | PR | IF | 0-0 | 23-25-16 | D06165J | 10 | | | D06167P | 2 | | | 150, 153-155, 162-165 | |
| 206Z | | | IF | 0-0 | 23-25-16 | D06165J | 22 | | | D06167P | REF | | IF | 150, 153-155, 162-165 | |
| 210B | 22 | PB | IJ | 5-0 | 23-25-17 | D06165J | 23 | | | D06167P | 12 | | | 150, 153-155, 162-165 | |
| 210R | 22 | PB | IJ | 0-0 | 23-25-17 | D06165J | 24 | | | D06167P | 13 | | | 150, 153-155, 162-165 | |
| 211B | 22 | PB | IK | 5-0 | 23-25-17 | D06165J | 26 | | | D06167P | 15 | | | 150, 153-155, 162-165 | |
| 211R | 22 | PB | IK | 0-0 | 23-25-17 | D06165J | 25 | | | D06167P | 14 | | | 150, 153-155, 162-165 | |
| FRE | | | | 0-0 | 23-25-16 | D06167P | 6 | | | D06167P | REF | | IE | 150, 153-155, 162-165 | |
| FRF | | | | 0-0 | 23-25-16 | D06167P | 3 | | | D06167P | REF | | IF | 150, 153-155, 162-165 | |

WIRE LIST

D280T132

91-21-11

Section W9010

Page 2 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | To | | | | |
|--------------|-----------------|-------------|----|--|-------------|----------|---------|------|------|--------|---------|------|-------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9020 | 286T9020 | | | SATCOM SYSTEM , E10 SHELF | | | | | | | | | | | |
| 004 | 22 | | PA | | 1-0 | 23-25-16 | D02651A | | D05 | | D02651A | | B05 | | 150, 153-155, 162-165 |
| 005 | 20 | | PA | | 2-0 | 23-25-16 | D02651C | | 1 | | D06167J | | 9 | | 150, 153-155, 162-165 |
| 006 | 20 | | PA | | 2-0 | 23-25-16 | D02651C | | 7 | | D06167J | | 10 | | 150, 153-155, 162-165 |
| 007 | 20 | | PA | | 2-0 | 23-25-16 | D02651C | | 8 | | D06167J | | 11 | | 150, 153-155, 162-165 |
| 201B | 22 | | PR | IA | 2-0 | 23-25-16 | D02651A | | D01 | | D06167J | | 1 | | 150, 153-155, 162-165 |
| 201R | 22 | | PR | IA | 0-0 | 23-25-16 | D02651A | | C01 | | D06167J | | 2 | | 150, 153-155, 162-165 |
| 201Z | | | | IA | 0-0 | 23-25-16 | D02651A | | DED | | D06167J | | 3 | | 150, 153-155, 162-165 |
| 202B | 22 | | PR | IB | 2-0 | 23-25-16 | D02651A | | B01 | | D06167J | | 4 | | 150, 153-155, 162-165 |
| 202R | 22 | | PR | IB | 0-0 | 23-25-16 | D02651A | | A01 | | D06167J | | 5 | | 150, 153-155, 162-165 |
| 202Z | | | | IB | 0-0 | 23-25-16 | D02651A | | DED | | D06167J | | 6 | | 150, 153-155, 162-165 |
| 901B | 22 | | PB | B | 0-0 | 23-25-17 | D02651A | | B03 | | D06167J | | 12 | | 150, 153-155, 162-165 |
| 901R | 22 | | PB | B | 2-0 | 23-25-17 | D02651A | | A03 | | D06167J | | 13 | | 150, 153-155, 162-165 |
| 902B | 22 | | PB | BL | 2-0 | 23-25-17 | D02651A | | D03 | | D06167J | | 15 | | 150, 153-155, 162-165 |
| 902R | 22 | | PB | BL | 0-0 | 23-25-17 | D02651A | | C03 | | D06167J | | 14 | | 150, 153-155, 162-165 |
| W9021 | 286T9021 | | | SATCOM SYSTEM,SIDE-MOUNTED HGA SUBSYSTEM-PORT | | | | | | | | | | | |
| 006 | 20 | | PA | | 5-0 | 23-25-17 | D02693 | | L | | GD06887 | | A.. 2 | | 150, 153-155, 162-165 |
| 007 | 20 | | PA | | 5-0 | 23-25-17 | D02693 | | B- | | GD06887 | | D.. 2 | | 150, 153-155, 162-165 |
| W9022 | 286T9022 | | | CUSTOMER WBA - VIDEO PROJECTION DISTRIBUTION | | | | | | | | | | | |
| 002 | 20 | | PA | | 10-0 | 23-32-13 | D09024 | | K | | SM00001 | | S | | 162-199 |
| 003 | 20 | | PA | | 10-0 | 23-32-13 | D09024 | | L | | SM00002 | | S | | 162-199 |
| 004 | 20 | | PA | | 10-0 | 23-32-13 | D09024 | | J | | SM00003 | | S | | 162-199 |
| 005 | 22 | | PA | | 10-0 | 23-32-13 | D09024 | | H | | SM00004 | | S | | 162-199 |
| 006 | 22 | | PA | | 10-0 | 23-32-13 | D09024 | | F | | SM00005 | | S | | 162-199 |
| 007 | 22 | | PA | | 10-0 | 23-32-13 | D09024 | | E | | SM00006 | | S | | 162-199 |
| 008 | 20 | | PA | | 10-0 | 23-32-13 | D09024 | | G | | SM00007 | | S | | 162-199 |
| 009 | 20 | | PA | | 10-0 | 23-32-13 | D09024 | | M | | SM00008 | | S | | 162-199 |
| 012 | 20 | | PA | | 15-0 | 23-32-13 | D09028 | | 1 | | SM00001 | | S | | 162-199 |
| 013 | 20 | | PA | | 15-0 | 23-32-13 | D09028 | | 4 | | SM00002 | | S | | 162-199 |
| 014 | 20 | | PA | | 15-0 | 23-32-13 | D09028 | | 5 | | SM00003 | | S | | 162-199 |
| 015 | 22 | | PA | | 15-0 | 23-32-13 | D09028 | | 6 | | SM00004 | | S | | 162-199 |
| 016 | 22 | | PA | | 15-0 | 23-32-13 | D09028 | | 8 | | SM00005 | | S | | 162-199 |
| 017 | 22 | | PA | | 15-0 | 23-32-13 | D09028 | | 7 | | SM00006 | | S | | 162-199 |
| 018 | 20 | | PA | | 15-0 | 23-32-13 | D09028 | | 3 | | SM00007 | | S | | 162-199 |
| 019 | 20 | | PA | | 15-0 | 23-32-13 | D09028 | | 2 | | SM00008 | | S | | 162-199 |
| 01CO | | | | A | 0-0 | 23-32-13 | D09028 | | = C1 | | D09026 | | = C1 | | 162-199 |
| 01CX | | | 5X | A | 25-0 | 23-32-13 | D09028 | | = A1 | | D09026 | | = A1 | | 162-199 |
| 022 | 20 | | PA | | 25-0 | 23-32-13 | D09027 | | 1 | | SM00001 | | S | | 162-199 |

WIRE LIST

D280T132

91-21-11

Section W9020

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | Effectivity | | | |
|------------------------|-----------------|----|----|---|-------------|----------|--------|------|------|--------|-------|------|---------|-------------|--------|--|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | | Splice | | |
| W9022 | 286T9022 | | | CUSTOMER WBA - VIDEO PROJECTION DISTRIBUTION (continued) | | | | | | | | | | | | | |
| 023 | 20 | | PA | | 25-0 | 23-32-13 | D09027 | | 4 | | | | SM00002 | | S | | 162-199 |
| 024 | 20 | | PA | | 25-0 | 23-32-13 | D09027 | | 5 | | | | SM00003 | | S | | 162-199 |
| 025 | 22 | | PA | | 25-0 | 23-32-13 | D09027 | | 6 | | | | SM00004 | | S | | 162-199 |
| 026 | 22 | | PA | | 25-0 | 23-32-13 | D09027 | | 8 | | | | SM00005 | | S | | 162-199 |
| 027 | 22 | | PA | | 25-0 | 23-32-13 | D09027 | | 7 | | | | SM00006 | | S | | 162-199 |
| 028 | 20 | | PA | | 25-0 | 23-32-13 | D09027 | | 3 | | | | SM00007 | | S | | 162-199 |
| 029 | 20 | | PA | | 25-0 | 23-32-13 | D09027 | | 2 | | | | SM00008 | | S | | 162-199 |
| 02CO | | | | B | 0-0 | 23-32-13 | D09027 | | =C1 | | | | D09020 | | =C1 | | 162-199 |
| 02CX | | 5X | | B | 25-0 | 23-32-13 | D09027 | | =A1 | | | | D09020 | | =A1 | | 162-199 |
| W9023 | 286T9023 | | | SATCOM SYSTEM,SIDE-MOUNTED HGA SUBSYSTEM-PORT | | | | | | | | | | | | | |
| 010 | 22 | | PA | | 5-0 | 23-25-17 | D02677 | | C | | | | D02693 | | V | | 150, 153-155, 162-165 |
| 011 | 22 | | PA | | 5-0 | 23-25-17 | D02677 | | B | | | | D02693 | | Y | | 150, 153-155, 162-165 |
| 013 | 20 | | PA | | 5-0 | 23-25-17 | D02677 | | A | | | | GD01750 | | D.. 2 | | 150, 153-155, 162-165 |
| 205B | 22 | | PB | IE | 5-0 | 23-25-17 | D02677 | | H | | | | D02693 | | K | | 150, 153-155, 162-165 |
| 205R | 22 | | PB | IE | 0-0 | 23-25-17 | D02677 | | F | | | | D02693 | | N | | 150, 153-155, 162-165 |
| W9024 | 286T9024 | | | SATCOM SYSTEM SIDE-MOUNTED HGA SUBSYSTEM-STRBD | | | | | | | | | | | | | |
| 002 | 20 | | PA | | 40-0 | 23-25-17 | D02689 | | M | | | | D06173J | | 4 | | 150, 153-155, 162-165 |
| 010 | 20 | | PA | | 3-0 | 23-25-17 | D02689 | | L | | | | GD06889 | | A.. 2 | | 150, 153-155, 162-165 |
| 011 | 20 | | PA | | 3-0 | 23-25-17 | D02689 | | B- | | | | GD06889 | | S.. 2 | | 150, 153-155, 162-165 |
| 012 | 22 | | PA | | 1-0 | 23-25-17 | D02689 | | B | | | | SM00001 | | W | | 150, 153-155, 162-165 |
| 017 | 22 | | PA | | 1-0 | 23-25-17 | D02689 | | C | | | | SM00001 | | W | | 150, 153-155, 162-165 |
| 018 | 22 | | PA | | 1-0 | 23-25-17 | D02689 | | D | | | | SM00001 | | W | | 150, 153-155, 162-165 |
| 201B | 22 | | PB | IA | 40-0 | 23-25-17 | D02689 | | H | | | | D06173J | | 2 | | 150, 153-155, 162-165 |
| 201R | 22 | | PB | IA | 0-0 | 23-25-17 | D02689 | | G | | | | D06173J | | 3 | | 150, 153-155, 162-165 |
| 202 | 20 | | UA | | 1-6 | 23-25-17 | D02689 | | REF | | IB | | GD06889 | | S.. 2 | | 150, 153-155, 162-165 |
| 202B | 22 | | PR | IB | 40-0 | 23-25-17 | D02689 | | U | | | | D06173J | | 5 | | 150, 153-155, 162-165 |
| 202R | 22 | | PR | IB | 0-0 | 23-25-17 | D02689 | | T | | | | D06173J | | 6 | | 150, 153-155, 162-165 |
| 202Z | | | | IB | 0-0 | 23-25-17 | D02689 | | REF | | IB | | D06173J | | 7 | | 150, 153-155, 162-165 |
| 203 | 20 | | PA | | 1-6 | 23-25-17 | D02689 | | REF | | IC | | GD06889 | | S.. 2 | | 150, 153-155, 162-165 |
| 203B | 22 | | PR | IC | 40-0 | 23-25-17 | D02689 | | X | | | | D06173J | | 8 | | 150, 153-155, 162-165 |
| 203R | 22 | | PR | IC | 0-0 | 23-25-17 | D02689 | | W | | | | D06173J | | 9 | | 150, 153-155, 162-165 |
| 203Z | | | | IC | 0-0 | 23-25-17 | D02689 | | REF | | IC | | D06173J | | 10 | | 150, 153-155, 162-165 |
| 204 | 20 | | UA | | 1-6 | 23-25-17 | D02689 | | REF | | ID | | GD06889 | | S.. 2 | | 150, 153-155, 162-165 |
| 204B | 22 | | PR | ID | 40-0 | 23-25-17 | D02689 | | R | | | | D06173J | | 11 | | 150, 153-155, 162-165 |
| 204R | 22 | | PR | ID | 0-0 | 23-25-17 | D02689 | | P | | | | D06173J | | 12 | | 150, 153-155, 162-165 |
| 204Z | | | | ID | 0-0 | 23-25-17 | D02689 | | REF | | ID | | D06173J | | 13 | | 150, 153-155, 162-165 |
| 205B | 22 | | PB | IE | 40-0 | 23-25-17 | D02689 | | F | | | | D06173J | | 14 | | 150, 153-155, 162-165 |

WIRE LIST

D280T132

91-21-11

Section W9020

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9024 | 286T9024 | | | SATCOM SYSTEM SIDE-MOUNTED HGA SUBSYSTEM-STRBD (continued) | | | | | | | | | | | |
| 205R | 22 | PB | | IE | 0-0 | 23-25-17 | D02689 | | E | | D06173J | | 15 | | 150, 153-155, 162-165 |
| W9025 | 286T9025 | | | COAX-SATCOM, M1787 HIGH PWR RLY TO M1789, LNA/DIP, L | | | | | | | | | | | |
| 013 | 22 | PA | | | 5-0 | 23-25-17 | D02717 | | H | | D02689 | | C- | | 150, 153-155, 162-165 |
| 014 | 22 | PA | | | 5-0 | 23-25-17 | D02717 | | B | | D02689 | | A- | | 150, 153-155, 162-165 |
| W9026 | 286T9026 | | | SATCOM ,E9-1 SHELF,LEFT | | | | | | | | | | | |
| 001 | 16 | PA | | | 2-9 | 23-25-11 | D06149P | | 21 | | TB0257H | | 3 | 2 | 150, 153-155, 162-165 |
| 002 | 20 | PA | | | 2-8 | 23-25-11 | D02647C | | 1 | | TB0257H | | 3 | 2 | 150, 153-155, 162-165 |
| 003 | 20 | PA | | | 2-6 | 23-25-11 | D02647C | | 8 | | GD00003 | | D.. | 2 | 150, 153-155, 162-165 |
| 004 | 20 | PA | | | 2-6 | 23-25-11 | D02647C | | 7 | | GD00003 | | A.. | 2 | 150, 153-155, 162-165 |
| 009 | 16 | PA | | | 0-7 | 23-25-11 | D06149P | | 23 | | TB0257H | | 1 | 2 | 150, 153-155, 162-165 |
| 010 | 22 | PA | | | 2-6 | 23-25-14 | D02647B | | C14 | | GD00003 | | S.. | 2 | 150, 153-155, 162-165 |
| 011 | 22 | PA | | | 2-4 | 23-25-14 | D06149P | | 25 | | D02647B | | B14 | | 150, 153-155, 162-165 |
| 012 | 22 | PQ | | AL | 2-4 | 23-25-14 | D06149P | | 27 | | D02647B | | A02 | | 150, 153-155, 162-165 |
| 012Z | | | | AL | 0-0 | 23-25-14 | D06149P | | 26 | | D02647B | | B02 | | 150, 153-155, 162-165 |
| 013 | 22 | PQ | | AM | 2-4 | 23-25-14 | D06149P | | 29 | | D02647B | | C02 | | 150, 153-155, 162-165 |
| 013Z | | | | AM | 0-0 | 23-25-14 | D06149P | | 28 | | D02647B | | D02 | | 150, 153-155, 162-165 |
| 014 | 22 | PA | | | 2-4 | 23-25-14 | D06149P | | 30 | | D02647B | | E08 | | 150, 153-155, 162-165 |
| 015 | 22 | PA | | | 2-4 | 23-25-14 | D06149P | | 31 | | D02647B | | F08 | | 150, 153-155, 162-165 |
| 016 | 22 | PQ | | AP | 2-2 | 23-25-14 | D02647B | | G02 | | D06155P | | 19 | | 150, 153-155, 162-165 |
| 016Z | | | | AP | 0-0 | 23-25-14 | D02647B | | H02 | | D06155P | | 18 | | 150, 153-155, 162-165 |
| 017 | 22 | PQ | | AQ | 2-2 | 23-25-14 | D02647B | | E02 | | D06155P | | 21 | | 150, 153-155, 162-165 |
| 017Z | | | | AQ | 0-0 | 23-25-14 | D02647B | | F02 | | D06155P | | 20 | | 150, 153-155, 162-165 |
| 018 | 22 | PA | | | 2-2 | 23-25-14 | D02647B | | G08 | | D06155P | | 22 | | 150, 153-155, 162-165 |
| 019 | 22 | PA | | | 2-2 | 23-25-14 | D02647B | | H08 | | D06155P | | 23 | | 150, 153-155, 162-165 |
| 022 | 20 | PA | | | 2-10 | 23-25-16 | D06165P | | 14 | | TB0257H | | 1 | 2 | 150, 153-155, 162-165 |
| 024 | 20 | PA | | | 3-7 | 23-25-17 | D06173P | | 1 | | TB0257H | | 1 | 2 | 150, 153-155, 162-165 |
| 025 | 20 | PA | | | 3-7 | 23-25-17 | D06173P | | 4 | | TB0257H | | 1 | 2 | 150, 153-155, 162-165 |
| 026 | 24 | PK | | | 2-9 | 23-25-15 | D02647B | | C13 | | D02701 | | 1 | | 150, 153-155, 162-164 |
| 026 | 22 | PK | | | 2-9 | 23-25-15 | D02647B | | C13 | | D02701 | | 1 | | 165 |
| 028 | 24 | PK | | | 2-9 | 23-25-15 | D02647B | | E13 | | D02701 | | 3 | | 150, 153-155, 162-164 |
| 028 | 22 | PK | | | 2-9 | 23-25-15 | D02647B | | E13 | | D02701 | | 3 | | 165 |
| 029 | 24 | PK | | | 2-9 | 23-25-15 | D02647B | | F13 | | D02701 | | 4 | | 150, 153-155, 162-164 |
| 029 | 22 | PK | | | 2-9 | 23-25-15 | D02647B | | F13 | | D02701 | | 4 | | 165 |
| 030 | 24 | PK | | | 2-9 | 23-25-15 | D02647B | | G13 | | D02701 | | 5 | | 150, 153-155, 162-164 |
| 030 | 22 | PK | | | 2-9 | 23-25-15 | D02647B | | G13 | | D02701 | | 5 | | 165 |
| 032 | 24 | PK | | | 2-9 | 23-25-15 | D02647B | | J13 | | D02701 | | 7 | | 155, 164 |
| 035 | 24 | PK | | | 2-9 | 23-25-15 | D02647B | | E14 | | D02701 | | 10 | | 150, 153-155, 162-164 |

WIRE LIST

D280T132

91-21-11
Section W9020
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W9026 | 286T9026 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | | |
| 035 | 22 | | PK | 2-9 | 23-25-15 | D02647B | | E14 | | | D02701 | | 10 | | 165 | |
| 036 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | F14 | | | D02701 | | 11 | | 150, 153-154, 162-163 | |
| 036 | 22 | | PK | 2-9 | 23-25-15 | D02647B | | F14 | | | D02701 | | 11 | | 165 | |
| 037 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | G14 | | | D02701 | | 12 | | 150, 153-155, 162-164 | |
| 037 | 22 | | PK | 2-9 | 23-25-15 | D02647B | | G14 | | | D02701 | | 12 | | 165 | |
| 038 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | H14 | | | D02701 | | 13 | | 150, 153-154, 162-163 | |
| 038 | 22 | | PK | 2-9 | 23-25-15 | D02647B | | H14 | | | D02701 | | 13 | | 165 | |
| 039 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | J14 | | | D02701 | | 14 | | 150, 153-154, 162-163 | |
| 039 | 22 | | PK | 2-9 | 23-25-15 | D02647B | | J14 | | | D02701 | | 14 | | 165 | |
| 040 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | K14 | | | D02701 | | 15 | | 150, 153-155, 162-164 | |
| 041 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | A15 | | | D02701 | | 16 | | 150, 153-155, 162-164 | |
| 042 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | B15 | | | D02701 | | 17 | | 150, 153-154, 162-163 | |
| 042 | 22 | | PK | 2-9 | 23-25-15 | D02647B | | B15 | | | D02701 | | 17 | | 165 | |
| 043 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | C15 | | | D02701 | | 18 | | 150, 153-155, 162-164 | |
| 044 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | D15 | | | D02701 | | 19 | | 154-155, 162-164 | |
| 044 | 22 | | PK | 2-9 | 23-25-15 | D02647B | | D15 | | | D02701 | | 19 | | 165 | |
| 045 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | E15 | | | D02701 | | 20 | | 150, 153, 155, 162-164 | |
| 046 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | F15 | | | D02701 | | 21 | | 154 | |
| 047 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | G15 | | | D02701 | | 22 | | 153-154 | |
| 048 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | H15 | | | D02701 | | 23 | | 154-155, 162-163 | |
| 048 | 22 | | PK | 2-9 | 23-25-15 | D02647B | | H15 | | | D02701 | | 23 | | 165 | |
| 049 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | J15 | | | D02701 | | 24 | | 154-155, 163-164 | |
| 050 | 24 | | PK | 2-9 | 23-25-15 | D02647B | | K15 | | | D02701 | | 25 | | 150, 153-155, 162-164 | |
| 050 | 22 | | PK | 2-9 | 23-25-15 | D02647B | | K15 | | | D02701 | | 25 | | 165 | |
| 051 | 20 | | PA | 3-1 | 23-25-17 | D06171P | | | 14 | | TB0257H | | 1 | 2 | 150, 153-155, 162-165 | |
| 052 | 20 | | PA | 3-1 | 23-25-17 | D06171P | | | 15 | | TB0257H | | 1 | 2 | 150, 153-155, 162-165 | |
| 053 | 20 | | PA | 2-0 | 23-25-12 | D02649C | | | 1 | | TB0257H | | 2 | 2 | 150, 153-155, 162-165 | |
| 054 | 18 | | PA | 2-6 | 23-25-12 | D02649C | | | 7 | | GDX0002 | | A.. | 2 | 150, 153-155, 162-165 | |
| 055 | 18 | | PA | 2-6 | 23-25-12 | D02649C | | | 8 | | GDX0002 | | S.. | 2 | 150, 153-155, 162-165 | |
| 082 | 24 | | PK | 2-9 | 23-25-15 | D02647A | | C11 | | | D02701 | | 32 | | 150, 153-155, 162-164 | |
| 082 | 22 | | PK | 2-9 | 23-25-15 | D02647A | | C11 | | | D02701 | | 32 | | 165 | |
| 086 | 24 | | PK | 2-9 | 23-25-15 | D02647A | | F13 | | | D02701 | | 36 | | 150, 153-155, 162-164 | |
| 086 | 22 | | PK | 2-9 | 23-25-15 | D02647A | | F13 | | | D02701 | | 36 | | 165 | |
| 087 | 24 | | PK | 2-9 | 23-25-15 | D02647A | | H13 | | | D02701 | | 37 | | 150, 153-155, 162-164 | |
| 087 | 22 | | PK | 2-9 | 23-25-15 | D02647A | | H13 | | | D02701 | | 37 | | 165 | |
| 088 | 24 | | PK | 2-9 | 23-25-15 | D02647A | | J12 | | | D02701 | | 38 | | 150, 153-155, 162-164 | |
| 088 | 22 | | PK | 2-9 | 23-25-15 | D02647A | | J12 | | | D02701 | | 38 | | 165 | |
| 089 | 24 | | PK | 2-9 | 23-25-15 | D02647A | | K12 | | | D02701 | | 39 | | 150, 153-155, 162-164 | |
| 089 | 22 | | PK | 2-9 | 23-25-15 | D02647A | | K12 | | | D02701 | | 39 | | 165 | |

WIRE LIST

D280T132

91-21-11

Section W9020

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|--------------|-----------------|----|-------|--|------|----------|---------|-------|------|------|---------|-------|------|------|-----------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W9026 | 286T9026 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | |
| 204B | 22 | PR | ID | | 2-8 | 23-25-16 | D02647B | H04 | | | TB0257H | 7 | 2 | | 150, 153-155, 162-165 |
| 204R | 22 | PR | ID | | 0-0 | 23-25-16 | D02647B | G04 | | | TB0257H | 5 | 2 | | 150, 153-155, 162-165 |
| 204Z | | | ID | | 0-0 | 23-25-16 | D02647B | DED | | | GDX0003 | S.. | 2 | | 150, 153-155, 162-165 |
| 206 | 20 | UA | | | 1-6 | 23-25-12 | D02649A | REF | IF | | GDX0001 | S.. | 2 | | 150, 153-155, 162-165 |
| 206B | 22 | PR | IF | | 2-10 | 23-25-12 | D02647B | F09 | | | D02649A | B01 | | | 150, 153-155, 162-165 |
| 206R | 22 | PR | IF | | 0-0 | 23-25-12 | D02647B | E09 | | | D02649A | A01 | | | 150, 153-155, 162-165 |
| 206Z | | | IF | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | IF | 150, 153-155, 162-165 |
| 207 | 20 | UA | | | 1-6 | 23-25-12 | D02649A | REF | IG | | GDX0001 | S.. | 2 | | 150, 153-155, 162-165 |
| 207B | 22 | PR | IG | | 2-10 | 23-25-12 | D02647B | H09 | | | D02649A | D01 | | | 150, 153-155, 162-165 |
| 207R | 22 | PR | IG | | 0-0 | 23-25-12 | D02647B | G09 | | | D02649A | C01 | | | 150, 153-155, 162-165 |
| 207Z | | | IG | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | IG | 150, 153-155, 162-165 |
| 208 | 20 | PA | | | 1-6 | 23-25-12 | D02649A | REF | IH | | GDX0001 | S.. | 2 | | 150, 153-155, 162-165 |
| 208B | 22 | PR | IH | | 2-10 | 23-25-12 | D02647B | K09 | | | D02649A | F01 | | | 150, 153-155, 162-165 |
| 208R | 22 | PR | IH | | 0-0 | 23-25-12 | D02647B | J09 | | | D02649A | E01 | | | 150, 153-155, 162-165 |
| 208Z | | | IH | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | IH | 150, 153-155, 162-165 |
| 209 | 20 | PA | | | 1-6 | 23-25-12 | D02649A | REF | II | | GDX0001 | S.. | 2 | | 150, 153-155, 162-165 |
| 209B | 22 | PR | II | | 2-10 | 23-25-12 | D02647B | B10 | | | D02649A | H01 | | | 150, 153-155, 162-165 |
| 209R | 22 | PR | II | | 0-0 | 23-25-12 | D02647B | A10 | | | D02649A | G01 | | | 150, 153-155, 162-165 |
| 209Z | | | II | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | II | 150, 153-155, 162-165 |
| 210 | 20 | PA | | | 1-6 | 23-25-12 | D02649A | REF | IJ | | GDX0001 | S.. | 2 | | 150, 153-155, 162-165 |
| 210B | 22 | PR | IJ | | 2-10 | 23-25-12 | D02647B | D10 | | | D02649A | K01 | | | 150, 153-155, 162-165 |
| 210R | 22 | PR | IJ | | 0-0 | 23-25-12 | D02647B | C10 | | | D02649A | J01 | | | 150, 153-155, 162-165 |
| 210Z | | | IJ | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | IJ | 150, 153-155, 162-165 |
| 211 | 20 | PA | | | 1-6 | 23-25-12 | D02649A | REF | IK | | GDX0001 | S.. | 2 | | 150, 153-155, 162-165 |
| 211B | 22 | PR | IK | | 2-10 | 23-25-12 | D02647B | F10 | | | D02649A | B03 | | | 150, 153-155, 162-165 |
| 211R | 22 | PR | IK | | 0-0 | 23-25-12 | D02647B | E10 | | | D02649A | A03 | | | 150, 153-155, 162-165 |
| 211Z | | | IK | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | IK | 150, 153-155, 162-165 |
| 212 | 20 | PA | | | 1-6 | 23-25-12 | D02649A | REF | IL | | GDX0001 | S.. | 2 | | 150, 153-155, 162-165 |
| 212B | 22 | PR | IL | | 2-10 | 23-25-12 | D02647B | H10 | | | D02649A | D03 | | | 150, 153-155, 162-165 |
| 212R | 22 | PR | IL | | 0-0 | 23-25-12 | D02647B | G10 | | | D02649A | C03 | | | 150, 153-155, 162-165 |
| 212Z | | | IL | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | IL | 150, 153-155, 162-165 |
| 213 | 20 | PA | | | 1-6 | 23-25-12 | D02649A | REF | IM | | GDX0001 | S.. | 2 | | 150, 153-155, 162-165 |
| 213B | 22 | PR | IM | | 2-10 | 23-25-12 | D02647B | K10 | | | D02649A | F03 | | | 150, 153-155, 162-165 |
| 213R | 22 | PR | IM | | 0-0 | 23-25-12 | D02647B | J10 | | | D02649A | E03 | | | 150, 153-155, 162-165 |
| 213Z | | | IM | | 0-0 | 23-25-12 | D02647B | DED | | | D02649A | REF | | IM | 150, 153-155, 162-165 |
| 216B | 24 | PW | IP | | 2-10 | 23-25-16 | D06165P | 18 | | | TB0257H | 7 | 2 | | 150, 153-155, 162-165 |
| 216R | 24 | PW | IP | | 0-0 | 23-25-16 | D06165P | 17 | | | TB0257H | 5 | 2 | | 150, 153-155, 162-165 |
| 216Z | | | IP | | 0-0 | 23-25-16 | D06165P | 19 | | | GDX0001 | S.. | 2 | | 150, 153-155, 162-165 |
| 217 | 20 | UA | | | 1-6 | 23-25-16 | D02647B | REF | IQ | | GDX0003 | S.. | 2 | | 150, 153-155, 162-165 |

WIRE LIST

D280T132

91-21-11

Section W9020

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|---------|-------|------|------|---------|-------|------|------|-----------------------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9026 | 286T9026 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | |
| 217B | 24 | PW | IQ | 2-5 | 23-25-16 | D02647B | F06 | | | D06165P | 21 | | | 150, 153-155, 162-165 | |
| 217R | 24 | PW | IQ | 0-0 | 23-25-16 | D02647B | E06 | | | D06165P | 20 | | | 150, 153-155, 162-165 | |
| 217Z | | | IQ | 0-0 | 23-25-16 | D02647B | REF | | IQ | D06165P | 22 | | | 150, 153-155, 162-165 | |
| 218B | 22 | PB | IR | 2-4 | 23-25-17 | D06171P | | 2 | | TB0257G | 33 | 2 | | 150, 153-155, 162-165 | |
| 218R | 22 | PB | IR | 0-0 | 23-25-17 | D06171P | | 1 | | TB0257G | 31 | 2 | | 150, 153-155, 162-165 | |
| 219B | 22 | PR | IS | 2-4 | 23-25-17 | D06171P | | 4 | | TB0257G | 35 | 2 | | 150, 153-155, 162-165 | |
| 219R | 22 | PR | IS | 0-0 | 23-25-17 | D06171P | | 3 | | TB0257G | 34 | 2 | | 150, 153-155, 162-165 | |
| 219Z | | | IS | 0-0 | 23-25-17 | D06171P | | 5 | | GD0003 | S.. | 2 | | 150, 153-155, 162-165 | |
| 220B | 22 | PR | IT | 2-9 | 23-25-17 | D06171P | | 7 | | TB0257G | 29 | 2 | | 150, 153-155, 162-165 | |
| 220R | 22 | PR | IT | 0-0 | 23-25-17 | D06171P | | 6 | | TB0257G | 27 | 2 | | 150, 153-155, 162-165 | |
| 220Z | | | IT | 0-0 | 23-25-17 | D06171P | | 8 | | GD0003 | S.. | 2 | | 150, 153-155, 162-165 | |
| 221B | 22 | PR | IU | 3-1 | 23-25-17 | D06171P | | 10 | | TB0257H | 7 | 2 | | 150, 153-155, 162-165 | |
| 221R | 22 | PR | IU | 0-0 | 23-25-17 | D06171P | | 9 | | TB0257H | 5 | 2 | | 150, 153-155, 162-165 | |
| 221Z | | | IU | 0-0 | 23-25-17 | D06171P | | 11 | | GD0001 | S.. | 2 | | 150, 153-155, 162-165 | |
| 222B | 22 | PB | IV | 1-11 | 23-25-17 | D06171P | | 13 | | D06165P | 23 | | | 150, 153-155, 162-165 | |
| 222R | 22 | PB | IV | 0-0 | 23-25-17 | D06171P | | 12 | | D06165P | 24 | | | 150, 153-155, 162-165 | |
| 224B | 22 | PB | IX | 2-4 | 23-25-17 | D06165P | | 26 | | D06173P | 2 | | | 150, 153-155, 162-165 | |
| 224R | 22 | PB | IX | 0-0 | 23-25-17 | D06165P | | 25 | | D06173P | 3 | | | 150, 153-155, 162-165 | |
| 225B | 22 | PR | IY | 3-7 | 23-25-17 | D06173P | | 5 | | TB0257H | 7 | 2 | | 150, 153-155, 162-165 | |
| 225R | 22 | PR | IY | 0-0 | 23-25-17 | D06173P | | 6 | | TB0257H | 5 | 2 | | 150, 153-155, 162-165 | |
| 225Z | | | IY | 0-0 | 23-25-17 | D06173P | | 7 | | GD0001 | S.. | 2 | | 150, 153-155, 162-165 | |
| 226B | 22 | PR | JA | 3-3 | 23-25-17 | D06173P | | 8 | | TB0257G | 29 | 2 | | 150, 153-155, 162-165 | |
| 226R | 22 | PR | JA | 0-0 | 23-25-17 | D06173P | | 9 | | TB0257G | 27 | 2 | | 150, 153-155, 162-165 | |
| 226Z | | | JA | 0-0 | 23-25-17 | D06173P | | 10 | | GD0003 | S.. | 2 | | 150, 153-155, 162-165 | |
| 227B | 22 | PR | JB | 2-10 | 23-25-17 | D06173P | | 11 | | TB0257G | 35 | 2 | | 150, 153-155, 162-165 | |
| 227R | 22 | PR | JB | 0-0 | 23-25-17 | D06173P | | 12 | | TB0257G | 34 | 2 | | 150, 153-155, 162-165 | |
| 227Z | | | JB | 0-0 | 23-25-17 | D06173P | | 13 | | GD0003 | S.. | 2 | | 150, 153-155, 162-165 | |
| 228B | 22 | PB | JC | 2-10 | 23-25-17 | D06173P | | 14 | | TB0257G | 33 | 2 | | 150, 153-155, 162-165 | |
| 228R | 22 | PB | JC | 0-0 | 23-25-17 | D06173P | | 15 | | TB0257G | 31 | 2 | | 150, 153-155, 162-165 | |
| 229 | 20 | PA | | 1-6 | 23-25-13 | D02647B | | | JD | GD0003 | S.. | 2 | | 150, 153-155, 162-165 | |
| 229B | 22 | PR | JD | 2-4 | 23-25-13 | D02647B | H01 | | | D06149P | 3 | | | 150, 153-155, 162-165 | |
| 229R | 22 | PR | JD | 0-0 | 23-25-13 | D02647B | G01 | | | D06149P | 2 | | | 150, 153-155, 162-165 | |
| 229Z | | | JD | 0-0 | 23-25-13 | D02647B | | | JD | D06149P | 1 | | | 150, 153-155, 162-165 | |
| 230 | 20 | PA | | 1-6 | 23-25-13 | D02647B | | | JE | GD0003 | S.. | 2 | | 150, 153-155, 162-165 | |
| 230B | 22 | PR | JE | 2-4 | 23-25-13 | D02647B | K01 | | | D06149P | 34 | | | 150, 153-155, 162-165 | |
| 230R | 22 | PR | JE | 0-0 | 23-25-13 | D02647B | J01 | | | D06149P | 33 | | | 150, 153-155, 162-165 | |
| 230Z | | | JE | 0-0 | 23-25-13 | D02647B | | | JE | D06149P | 32 | | | 150, 153-155, 162-165 | |
| 232 | 20 | PA | | 1-6 | 23-25-13 | D02647B | | | JG | GD0002 | S.. | 2 | | 150, 153-155, 162-165 | |
| 232B | 22 | PR | JG | 2-6 | 23-25-13 | D02647B | D03 | | | D06149P | 16 | | | 150, 153-155, 162-165 | |

WIRE LIST

D280T132

91-21-11

Section W9020

Page 6

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9026 | 286T9026 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | |
| 232R | 22 | PR | JG | 0-0 | 23-25-13 | D02647B | C03 | | | | D06149P | 15 | | | 150, 153-155, 162-165 |
| 232Z | | | JG | 0-0 | 23-25-13 | D02647B | | | JG | | D06149P | 14 | | | 150, 153-155, 162-165 |
| 233 | 20 | PA | | 1-6 | 23-25-13 | D02647B | | | JV | | GDX0003 | S.. | 2 | | 150, 153-155, 162-165 |
| 233B | 22 | PR | JV | 2-4 | 23-25-13 | D02647B | B06 | | | | D06149P | 19 | | | 150, 153-155, 162-165 |
| 233R | 22 | PR | JV | 0-0 | 23-25-13 | D02647B | A06 | | | | D06149P | 18 | | | 150, 153-155, 162-165 |
| 233Z | | | JV | 0-0 | 23-25-13 | D02647B | | | JV | | D06149P | 17 | | | 150, 153-155, 162-165 |
| 234B | 22 | PR | JI | 2-8 | 23-25-13 | D06149P | 24 | | | | TB0257G | 12 | 2 | | 150, 153-155, 162-165 |
| 234R | 22 | PR | JI | 0-0 | 23-25-13 | D06149P | 22 | | | | TB0257G | 11 | 2 | | 150, 153-155, 162-165 |
| 234Z | | | JI | 0-0 | 23-25-13 | D06149P | 20 | | | | GDX0002 | S.. | 2 | | 150, 153-155, 162-165 |
| 235B | 22 | PR | JJ | 2-6 | 23-25-13 | D02647B | K03 | | | | TB0257G | 12 | 2 | | 150, 153-155, 162-165 |
| 235R | 22 | PR | JJ | 0-0 | 23-25-13 | D02647B | J03 | | | | TB0257G | 11 | 2 | | 150, 153-155, 162-165 |
| 235Z | | | JJ | 0-0 | 23-25-13 | D02647B | DED | | | | GDX0002 | S.. | 2 | | 150, 153-155, 162-165 |
| 238B | 22 | PB | JM | 2-2 | 23-25-17 | D02647B | F07 | | | | TB0257G | 33 | 2 | | 150, 153-155, 162-165 |
| 238R | 22 | PB | JM | 0-0 | 23-25-17 | D02647B | E07 | | | | TB0257G | 31 | 2 | | 150, 153-155, 162-165 |
| 239B | 22 | PR | JN | 2-2 | 23-25-17 | D02647B | H07 | | | | TB0257G | 35 | 2 | | 150, 153-155, 162-165 |
| 239R | 22 | PR | JN | 0-0 | 23-25-17 | D02647B | G07 | | | | TB0257G | 34 | 2 | | 150, 153-155, 162-165 |
| 239Z | | | JN | 0-0 | 23-25-17 | D02647B | DED | | | | GDX0003 | S.. | 2 | | 150, 153-155, 162-165 |
| 240B | 22 | PR | JO | 2-4 | 23-25-17 | D02647B | K07 | | | | TB0257G | 29 | 2 | | 150, 153-155, 162-165 |
| 240R | 22 | PR | JO | 0-0 | 23-25-17 | D02647B | J07 | | | | TB0257G | 27 | 2 | | 150, 153-155, 162-165 |
| 240Z | | | JO | 0-0 | 23-25-17 | D02647B | DED | | | | GDX0003 | S.. | 2 | | 150, 153-155, 162-165 |
| 900B | 22 | PW | AA | 5-0 | 23-32-21 | D02647A | H02 | | | | D06165P | 3 | | | 150, 153-155, 162-165 |
| 900B | 22 | PR | AA | 5-0 | 23-32-21 | D02647A | H02 | | | | D06165P | 3 | | | 152, 156-157, 166-199 |
| 900R | 22 | PW | AA | 0-0 | 23-32-21 | D02647A | G02 | | | | D06165P | 2 | | | 150, 153-155, 162-165 |
| 900R | 22 | PR | AA | 0-0 | 23-32-21 | D02647A | G02 | | | | D06165P | 2 | | | 152, 156-157, 166-199 |
| 900Z | | | AA | 0-0 | 23-32-21 | D02647A | | | FA | | D06165P | 1 | | | 150, 152-199 |
| 901 | 22 | PA | | 2-4 | 23-25-13 | D02647B | A08 | | | | D06149P | 35 | | | 150, 153-155, 162-165 |
| 902 | 20 | PA | | 1-6 | 23-25-13 | D02647B | | | SL | | GDX0002 | S.. | 2 | | 150, 153-155, 162-165 |
| 902B | 22 | PR | SL | 2-4 | 23-25-13 | D02647B | C07 | | | | D06149P | 36 | | | 150, 153-155, 162-165 |
| 902R | 22 | PR | SL | 0-0 | 23-25-13 | D02647B | D07 | | | | D06149P | 37 | | | 150, 153-155, 162-165 |
| 902Z | | | SL | 0-0 | 23-25-13 | D02647B | | | SL | | D06149P | 38 | | | 150, 153-155, 162-165 |
| 903 | 22 | PA | | 5-0 | 23-32-21 | D06165P | 8 | | | | TB0257G | 20 | 2 | | 150, 152-199 |
| 904 | 20 | PA | | 1-6 | 23-25-13 | D02647B | | | SG | | GDX0002 | S.. | 2 | | 150, 153-155, 162-165 |
| 904B | 22 | PR | SG | 0-0 | 23-25-13 | D02647B | B07 | | | | D06165P | 40 | | | 150, 153-155, 162-165 |
| 904R | 22 | PR | SG | 2-4 | 23-25-13 | D02647B | A07 | | | | D06165P | 39 | | | 150, 153-155, 162-165 |
| 904Z | | | SG | 0-0 | 23-25-13 | D02647B | | | SG | | D06165P | 41 | | | 150, 153-155, 162-165 |
| 906 | 20 | PA | | 1-6 | 23-25-13 | D02647B | | | JS | | GDX0003 | S.. | 2 | | 150, 153-155, 162-165 |
| 906B | 22 | PR | JS | 0-0 | 23-25-13 | D02647B | F03 | | | | D06155P | 8 | | | 150, 153-155, 162-165 |
| 906R | 22 | PR | JS | 2-4 | 23-25-13 | D02647B | E03 | | | | D06155P | 7 | | | 150, 153-155, 162-165 |
| 906Z | | | JS | 0-0 | 23-25-13 | D02647B | | | JS | | D06155P | 6 | | | 150, 153-155, 162-165 |

WIRE LIST

D280T132

91-21-11

Section W9020

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|-------|------|------|---------|-------------|---|----|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W9026 | 286T9026 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | | | | |
| 907B | 22 | | PR | JT | 0-0 | 23-25-13 | D06155P | | 5 | | | | | TB0257G | 12 | 2 | | 150, 153-155, 162-165 |
| 907R | 22 | | PR | JT | 3-0 | 23-25-13 | D06155P | | 4 | | | | | TB0257G | 11 | 2 | | 150, 153-155, 162-165 |
| 907Z | | | | JT | 0-0 | 23-25-13 | D06155P | | 24 | | | | | GD00002 | S.. | 2 | | 150, 153-155, 162-165 |
| 908 | 20 | | PA | | 1-6 | 23-25-14 | D02647B | | | | | JH | | GD00002 | S.. | 2 | | 150, 153-155, 162-165 |
| 908B | 22 | | PR | JH | 2-4 | 23-25-14 | D02647B | | | K02 | | | | D06173P | 20 | | | 150, 153-155, 162-165 |
| 908R | 22 | | PR | JH | 0-0 | 23-25-14 | D02647B | | | J02 | | | | D06173P | 19 | | | 150, 153-155, 162-165 |
| 908Z | | | | JH | 0-0 | 23-25-14 | D02647B | | | | | JH | | D06173P | 21 | | | 150, 153-155, 162-165 |
| 909 | 20 | | PA | | 1-6 | 23-25-14 | D02647B | | | | | JZ | | GD00002 | S.. | 2 | | 150, 153-155, 162-165 |
| 909B | 22 | | PR | JZ | 2-4 | 23-25-14 | D02647B | | | B03 | | | | D06173P | 23 | | | 150, 153-155, 162-165 |
| 909R | 22 | | PR | JZ | 0-0 | 23-25-14 | D02647B | | | A03 | | | | D06173P | 22 | | | 150, 153-155, 162-165 |
| 909Z | | | | JZ | 0-0 | 23-25-14 | D02647B | | | | | JZ | | D06173P | 24 | | | 150, 153-155, 162-165 |
| 910 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 1 | | | | | D02647A | G01 | | | 150, 153-155, 162-165 |
| 911 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 2 | | | | | D02647A | J01 | | | 150, 153-155, 162-165 |
| 912 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 3 | | | | | D02647A | A03 | | | 150, 153-155, 162-165 |
| 913 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 4 | | | | | D02647A | B03 | | | 150, 153-155, 162-165 |
| 914 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 5 | | | | | D02647A | C03 | | | 150, 153-155, 162-165 |
| 915 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 6 | | | | | D02647A | D03 | | | 150, 153-155, 162-165 |
| 916 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 7 | | | | | D02647A | E03 | | | 150, 153-155, 162-165 |
| 917 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 8 | | | | | D02647A | H01 | | | 150, 153-155, 162-165 |
| 918 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 9 | | | | | D02647A | K01 | | | 150, 153-155, 162-165 |
| 919 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 10 | | | | | D02647B | A13 | | | 150, 153-155, 162-165 |
| 920 | 20 | | PA | | 2-8 | 23-25-13 | D96101P | | 11 | | | | | TB0257H | 9 | 2 | | 150, 153-155, 162-165 |
| 921 | 20 | | PA | | 2-6 | 23-25-13 | D96101P | | 12 | | | | | GD00002 | D.. | 2 | | 150, 153-155, 162-165 |
| 922 | 20 | | PA | | 2-4 | 23-25-13 | D06149P | | 39 | | | | | TB0257H | 9 | 2 | | 150, 153-155, 162-165 |
| 925 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 13 | | | | | D02647A | A01 | | | 150, 153-155, 162-165 |
| 926 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 14 | | | | | D02647A | C01 | | | 150, 153-155, 162-165 |
| 927 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 15 | | | | | D02647A | D01 | | | 150, 153-155, 162-165 |
| 928 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 16 | | | | | D02647A | G15 | | | 150, 153-155, 162-165 |
| 929 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 17 | | | | | D02647A | K15 | | | 150, 153-155, 162-165 |
| 930 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 18 | | | | | D02647A | F15 | | | 150, 153-155, 162-165 |
| 931 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 19 | | | | | D02647A | J15 | | | 150, 153-155, 162-165 |
| 932 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 20 | | | | | D02647A | H15 | | | 150, 153-155, 162-165 |
| 933 | 22 | | PA | | 2-4 | 23-25-13 | D96101P | | 21 | | | | | D02647A | C15 | | * | 150, 153-155, 162-165 |
| 934 | 20 | | PA | | 1-6 | 23-25-13 | D02647B | | | | | SM | | GD00002 | D.. | 2 | | 150, 153-155, 162-165 |
| 934B | 22 | | PR | SM | 0-0 | 23-25-13 | D96101P | | 23 | | | | | D02647B | B01 | | | 150, 153-155, 162-165 |
| 934R | 22 | | PR | SM | 2-4 | 23-25-13 | D96101P | | 22 | | | | | D02647B | A01 | | | 150, 153-155, 162-165 |
| 934Z | | | | SM | 0-0 | 23-25-13 | D96101P | | | | | SD | | D02647B | | | SM | 150, 153-155, 162-165 |
| 936B | 22 | | PR | SD | 0-0 | 23-25-13 | D96101P | | 25 | | | | | D02647B | D01 | | | 150, 153-155, 162-165 |
| 936R | 22 | | PR | SD | 2-4 | 23-25-13 | D96101P | | 24 | | | | | D02647B | C01 | | | 150, 153-155, 162-165 |

WIRE LIST

D280T132

91-21-11

Section W9020

Page 8

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|-------------|----|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W9026 | 286T9026 | | | SATCOM ,E9-1 SHELF,LEFT (continued) | | | | | | | | | | | | |
| 936Z | | | | SD | 0-0 | 23-25-13 | D96101P | | | | SD | D02647B | | | SM | 150, 153-155, 162-165 |
| 938 | 20 | | PA | | 2-8 | 23-25-13 | D96101P | 26 | | | | TB0257H | 9 | 2 | | 150, 153-155, 162-165 |
| 939 | 20 | | PA | | 2-8 | 23-25-13 | D96101P | 27 | | | | TB0257H | 3 | 2 | | 150, 153-155, 162-165 |
| 940 | 20 | | PA | | 2-4 | 23-25-13 | D96101P | 28 | | | | GDX0002 | D.. | 2 | | 150, 153-155, 162-165 |
| 942 | 22 | | PA | | 5-0 | 23-32-21 | D06165P | 7 | | | | D02647A | B01 | | | 150, 152-199 |
| 943 | 22 | | PA | | 5-0 | 23-32-21 | D06165P | 9 | | | | D02647A | E01 | | | 150, 152-199 |
| 944 | 22 | | PA | | 5-0 | 23-32-21 | D02647A | C15 | | * | | TB0257G | 20 | 2 | | 150, 153-155, 162-165 |
| 944 | 22 | | PA | | 5-0 | 23-32-21 | D02647A | C15 | | | | TB0257G | 20 | 2 | | 152, 156-157, 166-199 |
| 945 | 20 | | PA | | 3-0 | 23-32-21 | D02647A | | | | FA | GDX0002 | S.. | 2 | | 150, 152-199 |
| 946 | 24 | | PK | | 2-9 | 23-25-15 | D02647A | B11 | | | | D02701 | 45 | | | 150, 153-155, 162-164 |
| 946 | 22 | | PK | | 2-9 | 23-25-15 | D02647A | B11 | | | | D02701 | 45 | | | 165 |
| 947 | 24 | | PK | | 2-9 | 23-25-15 | D02647A | H11 | | | | D02701 | 46 | | | 150, 153-155, 162-164 |
| 947 | 22 | | PK | | 2-9 | 23-25-15 | D02647A | H11 | | | | D02701 | 46 | | | 165 |
| 948 | 24 | | PK | | 2-9 | 23-25-15 | D02647A | G13 | | | | D02701 | 47 | | | 150, 153-155, 162-164 |
| 948 | 22 | | PK | | 2-9 | 23-25-15 | D02647A | G13 | | | | D02701 | 47 | | | 165 |
| 949 | 24 | | PK | | 2-9 | 23-25-15 | D02647A | J13 | | | | D02701 | 48 | | | 150, 153-155, 162-164 |
| 949 | 22 | | PK | | 2-9 | 23-25-15 | D02647A | J13 | | | | D02701 | 48 | | | 165 |
| 950 | 22 | | PA | | 2-4 | 23-25-14 | D02647B | C11 | | | | D06149P | 7 | | | 150, 153-155, 162-165 |
| 951 | 22 | | PA | | 2-4 | 23-25-14 | D02647B | D11 | | | | D06155P | 9 | | | 150, 153-155, 162-165 |
| 952B | 22 | | PW | AB | 5-0 | 23-32-21 | D06165P | 5 | | | | D02647A | F02 | | | 150, 153-155, 162-165 |
| 952B | 22 | | PR | AB | 5-0 | 23-32-21 | D06165P | 5 | | | | D02647A | F02 | | | 152, 156-157, 166-199 |
| 952R | 22 | | PW | AB | 0-0 | 23-32-21 | D06165P | 4 | | | | D02647A | E02 | | | 150, 153-155, 162-165 |
| 952R | 22 | | PR | AB | 0-0 | 23-32-21 | D06165P | 4 | | | | D02647A | E02 | | | 152, 156-157, 166-199 |
| 952Z | | | | AB | 0-0 | 23-32-21 | D06165P | 6 | | | | D02647A | DED | | | 150, 152-199 |
| FRD | | | | | 0-0 | 23-25-13 | D96101P | 29 | | | | D96101P | | | SD | 150, 153-155, 162-165 |

WIRE LIST
D280T132

91-21-11
Section W9020
Page 9 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|------|-------------|---------|-------|------|------|---------|-------|------|------|-----------------------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W9030 | 286T9030 | SATCOM - E2-6 TO P5 PNL (CUSTOMER) | | | | | | | | | | | | | | |
| 006 | 20 | | PA | 7-0 | 33-13-16 | D02695 | | 1 | | TB0068H | | 3 | | 150, 153-155, 162-165 | | |
| 007 | 20 | | PA | 7-0 | 33-13-16 | D02695 | | 2 | | GD00267 | | A.. | 2 | 150, 153-155, 162-165 | | |
| 010 | 20 | | PA | 7-0 | 33-16-17 | D02695 | | 3 | | TB0070Y | A031 | BJ | | 150, 153-155, 162-165 | | |
| 011 | 20 | | PA | 7-0 | 33-16-17 | D02695 | | 4 | | TB0070Z | | 34 | BJ | 150, 153-155, 162-165 | | |
| 021 | 20 | | PA | 7-0 | 23-25-14 | D02695 | | 13 | | GD00267 | | D.. | 2 | 150, 153-155, 162-165 | | |
| 901 | 22 | | PA | 35-0 | 23-25-14 | D02695 | | 15 | | D04657J | | 12 | | 150, 153-155, 162-165 | | |
| 902 | 22 | | PA | 35-0 | 23-25-14 | D02695 | | 7 | | D04657J | | 2 | | 150, 153-155, 162-165 | | |
| 903 | 22 | | PA | 35-0 | 23-25-14 | D02695 | | 12 | | D04657J | | 1 | | 150, 153-155, 162-165 | | |
| 904 | 22 | | PA | 35-0 | 23-25-14 | D02695 | | 14 | | D04653J | | 12 | | 150, 153-155, 162-165 | | |
| 905 | 22 | | PA | 35-0 | 23-25-14 | D02695 | | 6 | | D04653J | | 2 | | 150, 153-155, 162-165 | | |
| 906 | 22 | | PA | 35-0 | 23-25-14 | D02695 | | 11 | | D04653J | | 1 | | 150, 153-155, 162-165 | | |
| W9031 | 286T9031 | SATCOM SYSTEM,SIDE-MOUNTED HGA SUBSYSTEM-PORT | | | | | | | | | | | | | | |
| 002 | 20 | | PA | 5-0 | 23-25-17 | D02709 | | F | | D06171J | | 15 | | 150, 153-155, 162-165 | | |
| 008 | 20 | | PA | 5-0 | 23-25-17 | D02709 | | E | | GD01750 | | A.. | 2 | 150, 153-155, 162-165 | | |
| 009 | 20 | | PA | 5-0 | 23-25-17 | D02709 | | A | | GD01750 | | S.. | 2 | 150, 153-155, 162-165 | | |
| W9032 | 286T9032 | COAX-SATCOM, M1787 HIGHPWR RLY TO M1789, LNA/DIP, L | | | | | | | | | | | | | | |
| 001 | 20 | | PA | 5-0 | 23-25-17 | D02717 | | F | | D06173J | | 1 | | 150, 153-155, 162-165 | | |
| 003 | 20 | | PA | 5-0 | 23-25-17 | D02717 | | E | | GD01750 | | A.. | 2 | 150, 153-155, 162-165 | | |
| 004 | 20 | | PA | 5-0 | 23-25-17 | D02717 | | A | | GD01750 | | S.. | 2 | 150, 153-155, 162-165 | | |
| W9033 | 286T9033 | COAX-SATCOM, M1787 HIGHPWR RLY TO M1789, LNA/DIP, L | | | | | | | | | | | | | | |
| 015 | 22 | | PA | 5-0 | 23-25-17 | D02677 | | D | | D02689 | | Y | | 150, 153-155, 162-165 | | |
| W9034 | 286T9034 | COAX-SATCOM, M1787 HIGHPWR RLY TO M1789, LNA/DIP, L | | | | | | | | | | | | | | |
| 205B | 26 | BW | IA | 25-4 | 23-25-14 | D06173J | | 20 | | D09065P | | F | | 150, 152-199 | | |
| 205G | 26 | BW | IB | 0-0 | 23-25-14 | D06173J | | 22 | | D09065P | | B | | 150, 152-199 | | |
| 205R | 26 | BW | IA | 0-0 | 23-25-14 | D06173J | | 19 | | D09065P | | E | | 150, 152-199 | | |
| 205Y | 26 | BW | IB | 0-0 | 23-25-14 | D06173J | | 23 | | D09065P | | C | | 150, 152-199 | | |
| 205Z | | | IA | 0-0 | 23-25-14 | D06173J | | 21 | | D09065P | | | FA | 150, 152-199 | | |
| 206Z | | | IB | 0-0 | 23-25-14 | D06173J | | 24 | | D09065P | | | FA | 150, 152-199 | | |
| FRA | | | | 0-0 | 23-25-14 | D09065P | | D | | D09065P | | | FA | 150, 152-199 | | |
| YAA | | | | 0-0 | 23-25-14 | D06173J | | =CC | D | D09065P | | =CC | D | 150, 152-199 | | |
| W9035 | 286T9035 | SATCOM SYSTEM,SIDE-MOUNTED HGA SUBSYSTEM-PORT | | | | | | | | | | | | | | |
| 001 | 20 | | PA | 51-0 | 23-25-17 | D06171J | | 14 | | D02693 | | M | | 150, 153-155, 162-165 | | |
| 014 | 22 | | PA | 1-0 | 23-25-17 | D02693 | | A | | SM00001 | | | W | 150, 153-155, 162-165 | | |

WIRE LIST

D280T132

91-21-11

Section W9030

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9035 | 286T9035 | | | SATCOM SYSTEM,SIDE-MOUNTED HGA SUBSYSTEM-PORT (continued) | | | | | | | | | | | |
| 016 | 22 | | PA | | 1-0 | 23-25-17 | D02693 | | D | | SM00001 | | W | | 150, 153-155, 162-165 |
| 017 | 22 | | PA | | 1-0 | 23-25-17 | D02693 | | C | | SM00001 | | W | | 150, 153-155, 162-165 |
| 201B | 22 | | PB | IA | 51-0 | 23-25-17 | D06171J | | 2 | | D02693 | | F | | 150, 153-155, 162-165 |
| 201R | 22 | | PB | IA | 0-0 | 23-25-17 | D06171J | | 1 | | D02693 | | E | | 150, 153-155, 162-165 |
| 202 | 20 | | UA | | 1-6 | 23-25-17 | D02693 | | REF | IB | GD06887 | | D.. | 2 | 150, 153-155, 162-165 |
| 202B | 22 | | PR | IB | 51-0 | 23-25-17 | D06171J | | 4 | | D02693 | | X | | 150, 153-155, 162-165 |
| 202R | 22 | | PR | IB | 0-0 | 23-25-17 | D06171J | | 3 | | D02693 | | W | | 150, 153-155, 162-165 |
| 202Z | | | | IB | 0-0 | 23-25-17 | D06171J | | 5 | | D02693 | | REF | | IB 150, 153-155, 162-165 |
| 203 | 20 | | UA | | 1-6 | 23-25-17 | D02693 | | REF | IC | GD06887 | | D.. | 2 | 150, 153-155, 162-165 |
| 203B | 22 | | PR | IC | 51-0 | 23-25-17 | D06171J | | 7 | | D02693 | | R | | 150, 153-155, 162-165 |
| 203R | 22 | | PR | IC | 0-0 | 23-25-17 | D06171J | | 6 | | D02693 | | P | | 150, 153-155, 162-165 |
| 203Z | | | | IC | 0-0 | 23-25-17 | D06171J | | 8 | | D02693 | | REF | | IC 150, 153-155, 162-165 |
| 204 | 20 | | UA | | 1-6 | 23-25-17 | D02693 | | REF | ID | GD06887 | | D.. | 2 | 150, 153-155, 162-165 |
| 204B | 22 | | PR | ID | 51-0 | 23-25-17 | D06171J | | 10 | | D02693 | | U | | 150, 153-155, 162-165 |
| 204R | 22 | | PR | ID | 0-0 | 23-25-17 | D06171J | | 9 | | D02693 | | T | | 150, 153-155, 162-165 |
| 204Z | | | | ID | 0-0 | 23-25-17 | D06171J | | 11 | | D02693 | | REF | | ID 150, 153-155, 162-165 |
| 206B | 22 | | PB | IF | 51-0 | 23-25-17 | D06171J | | 13 | | D02693 | | H | | 150, 153-155, 162-165 |
| 206R | 22 | | PB | IF | 0-0 | 23-25-17 | D06171J | | 12 | | D02693 | | G | | 150, 153-155, 162-165 |
| W9036 | 286T9036 | | | SATCOM SYSTEM,SIDE-MOUNTED HGA SUBSYSTEM-PORT | | | | | | | | | | | |
| 004 | 24 | | PK | | 9-0 | 23-25-17 | D02693 | | A- | | D02709 | | B | | 150, 153-155, 162-165 |
| 005 | 24 | | PK | | 9-0 | 23-25-17 | D02693 | | C- | | D02709 | | H | | 150, 153-155, 162-165 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|--------------|-----------------|--|-------|-------------|------|----------|---------|-------|------|------|---------|-------|-------------|------|--------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W9040 | 286T9040 | AIR TO GROUND TELEPHONE - POWER DISTRIBUTION | | | | | | | | | | | | | |
| 900 | 10 | | PA | | 3-0 | 23-19-11 | E090-90 | =G | E | | GD09003 | S.. | E | | 150, 152-199 |
| 901 | 20 | | PA | | 5-0 | 23-19-11 | D09061J | | 2 | | D09062A | | | * | 150, 152-199 |
| 902 | 16 | | PA | | 5-0 | 23-19-11 | D09062A | | 7 | * | D09060P | D- | | | 150, 152-199 |
| 903 | 20 | | PA | | 5-0 | 23-19-11 | D09061J | | 1 | | D09062A | 6 | | *1 | 150, 152-199 |
| 904 | 16 | | PA | | 5-0 | 23-19-11 | D09062A | | 6 | *1 | D09060P | C- | | | 150, 152-199 |
| 905B | 16 | | Q5 | A | 0-0 | 23-19-11 | D09060P | | Z | | D09062A | 10 | | | 150, 152-199 |
| 905G | 16 | | Q5 | A | 0-0 | 23-19-11 | D09060P | | Y | | D09062A | 11 | | | 150, 152-199 |
| 905O | 16 | | Q5 | A | 0-0 | 23-19-11 | D09060P | | X | | D09062A | 12 | | | 150, 152-199 |
| 905W | 16 | | Q5 | A | 5-0 | 23-19-11 | D09060P | | A- | | D09062A | 9 | | | 150, 152-199 |
| 905Z | | | | A | 0-0 | 23-19-11 | D09060P | | B- | | D09062A | 13 | | | 150, 152-199 |
| 906B | 16 | | Q5 | B | 0-0 | 23-19-11 | D09060P | | U | | D09062A | 18 | | | 150, 152-199 |
| 906G | 16 | | Q5 | B | 0-0 | 23-19-11 | D09060P | | T | | D09062A | 19 | | | 150, 152-199 |
| 906O | 16 | | Q5 | B | 0-0 | 23-19-11 | D09060P | | S | | D09062A | 20 | | | 150, 152-199 |
| 906W | 16 | | Q5 | B | 5-0 | 23-19-11 | D09060P | | V | | D09062A | 17 | | | 150, 152-199 |
| 906Z | | | | B | 0-0 | 23-19-11 | D09060P | | W | | D09062A | 21 | | | 150, 152-199 |
| 907B | 16 | | Q5 | C | 0-0 | 23-19-11 | D09060P | | N | | D09062B | 3 | | | 150, 152-199 |
| 907G | 16 | | Q5 | C | 0-0 | 23-19-11 | D09060P | | M | | D09062B | 2 | | | 150, 152-199 |
| 907O | 16 | | Q5 | C | 0-0 | 23-19-11 | D09060P | | L | | D09062B | 4 | | | 150, 152-199 |
| 907W | 16 | | Q5 | C | 5-0 | 23-19-11 | D09060P | | P | | D09062B | 1 | | | 150, 152-199 |
| 907Z | | | | C | 0-0 | 23-19-11 | D09060P | | R | | D09062B | 5 | | | 150, 152-199 |
| 908B | 16 | | Q5 | D | 0-0 | 23-19-11 | D09060P | | H | | D09062B | 10 | | | 150, 152-199 |
| 908G | 16 | | Q5 | D | 0-0 | 23-19-11 | D09060P | | G | | D09062B | 11 | | | 150, 152-199 |
| 908O | 16 | | Q5 | D | 0-0 | 23-19-11 | D09060P | | F | | D09062B | 12 | | | 150, 152-199 |
| 908W | 16 | | Q5 | D | 5-0 | 23-19-11 | D09060P | | J | | D09062B | 9 | | | 150, 152-199 |
| 908Z | | | | D | 0-0 | 23-19-11 | D09060P | | K | | D09062B | 13 | | | 150, 152-199 |
| 909B | 16 | | Q5 | E | 0-0 | 23-19-11 | D09060P | | B | | D09062B | 18 | | | 150, 152-199 |
| 909G | 16 | | Q5 | E | 0-0 | 23-19-11 | D09060P | | C | | D09062B | 19 | | | 150, 152-199 |
| 909O | 16 | | Q5 | E | 0-0 | 23-19-11 | D09060P | | A | | D09062B | 20 | | | 150, 152-199 |
| 909W | 16 | | Q5 | E | 5-0 | 23-19-11 | D09060P | | D | | D09062B | 17 | | | 150, 152-199 |
| 909Z | | | | E | 0-0 | 23-19-11 | D09060P | | E | | D09062B | 21 | | | 150, 152-199 |
| W9041 | 286T9041 | AIR TO GROUND PUBLIC TELEPHONE - 115V AC UNTILTY BUS - LEFT | | | | | | | | | | | | | |
| 001B | 10 | | Q3 | A | 0-0 | 24-51-13 | C09040 | B01 | D | | TB5130 | 5 | E | | 150, 152-199 |
| 001O | 10 | | Q3 | A | 0-0 | 24-51-13 | TB5130 | | 6 | E | C09040 | C01 | D | | 150, 152-199 |
| 001W | 10 | | Q3 | A | 5-0 | 24-51-13 | C09040 | A01 | D | | TB5130 | 4 | E | | 150, 152-199 |
| W9042 | 286T9042 | AIR TO GROUND PUBLIC TELEPHONE - POWER | | | | | | | | | | | | | |
| 901B | 10 | | Q3 | AA | 0-0 | 23-19-11 | C09040 | B2 | D | | K09035 | B1 | D | | 150, 152-199 |
| 901O | 10 | | Q3 | AA | 0-0 | 23-19-11 | C09040 | C2 | D | | K09035 | C1 | D | | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W9040

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9042 | 286T9042 | | | AIR TO GROUND PUBLIC TELEPHONE - POWER (continued) | | | | | | | | | | | |
| 901W | 10 | Q3 | | AA | 5-0 | 23-19-11 | C09040 | A2 | D | | K09035 | A1 | D | | 150, 152-199 |
| 902 | 20 | PA | | | 3-0 | 23-19-11 | GDZ9001 | S.. | E | | K09035 | X2 | D | | 150, 152-199 |
| W9043 | 286T9043 | | | AIR TO GROUND PUBLIC TELEPHONE - POWER | | | | | | | | | | | |
| 901B | 10 | Q3 | | AA | 0-0 | 23-19-11 | D04906J | 2 | EO | | K09035 | B2 | D | | 150, 152-199 |
| 901O | 10 | Q3 | | AA | 0-0 | 23-19-11 | D04906J | 4 | EO | | K09035 | C2 | D | | 150, 152-199 |
| 901W | 10 | Q3 | | AA | 5-0 | 23-19-11 | D04906J | 1 | EO | | K09035 | A2 | D | | 150, 152-199 |
| 902 | 20 | PA | | | 5-0 | 23-19-11 | D04906J | 5 | EO | | K09035 | X1 | D | | 150, 152-199 |
| W9044 | 286T9044 | | | AIR TO GROUND PUBLIC TELEPHONE - POWER | | | | | | | | | | | |
| 901 | 10 | PA | | | 3-0 | 23-19-11 | D09062C | 6 | | | GD09004 | S.. | E | | 150, 152-199 |
| 902B | 10 | Q3 | | AA | 0-0 | 23-19-11 | D09062C | 4 | | | D04906P | 2 | EO | | 150, 152-199 |
| 902O | 10 | Q3 | | AA | 0-0 | 23-19-11 | D09062C | 5 | | | D04906P | 4 | EO | | 150, 152-199 |
| 902W | 10 | Q3 | | AA | 14-6 | 23-19-11 | D09062C | 3 | | | D04906P | 1 | EO | | 150, 152-199 |
| W9045 | 286T9045 | | | P6 - MN PWR DISTR DISTR PNL - AIR TO GROUND PUBLIC TELEPHONE | | | | | | | | | | | |
| 901 | 10 | PA | | | 5-0 | 24-32-11 | C09041 | 2 | D | | C00886 | 2 | D | | 150, 152-199 |
| W9046 | 286T9046 | | | AIR TO GROUND PUBLIC TELEPHONE - CONTROL POWER | | | | | | | | | | | |
| 901 | 20 | PA | | | 5-0 | 23-19-11 | D05848J | 1 | | | C09041 | 1 | D | | 150, 152-199 |
| W9047 | 286T9047 | | | AIR GROUND PUBLIC TELEPHONE - CONTROL & TEST/SERVICE | | | | | | | | | | | |
| 900 | 24 | PK | | | 19-0 | 23-19-11 | D09110P | 1 | | | D09063P | H | | | 150, 152-199 |
| 901 | 24 | PK | | | 19-0 | 23-19-11 | D09110P | 2 | | | D09063P | J | | | 150, 152-199 |
| 902 | 24 | PK | | | 14-6 | 23-19-11 | D04906P | 11 | | | D09063P | J- | | | 150, 152-199 |
| 903 | 24 | PK | | | 14-6 | 23-19-11 | D04906P | 32 | | | D09063P | I- | | | 150, 152-199 |
| 904B | 24 | PX | | A | 0-0 | 23-19-11 | D09064J | 9 | | | D09063P | CAP | Y | | 150, 152-199 |
| 904O | 24 | PX | | A | 0-0 | 23-19-11 | D09064J | 10 | | | D09063P | CAP | Y | | 150, 152-199 |
| 904W | 24 | PX | | A | 20-2 | 23-19-11 | D09064J | 8 | | | D09063P | CAP | Y | | 150, 152-199 |
| 904Z | | | | A | 0-0 | 23-19-11 | D09064J | DED | | | D09063P | REF | %A | | 150, 152-199 |
| 905B | 24 | PX | | B | 0-0 | 23-19-11 | D09064J | 3 | | | D09063P | CAP | Y | | 150, 152-199 |
| 905O | 24 | PX | | B | 0-0 | 23-19-11 | D09064J | 5 | | | D09063P | CAP | Y | | 150, 152-199 |
| 905W | 24 | PX | | B | 20-2 | 23-19-11 | D09064J | 2 | | | D09063P | CAP | Y | | 150, 152-199 |
| 905Z | | | | B | 0-0 | 23-19-11 | D09064J | DED | | | D09063P | REF | %A | | 150, 152-199 |
| 906B | 24 | PX | | C | 0-0 | 23-19-11 | D09064J | 7 | | | D09063P | M- | | | 150, 152-199 |
| 906O | 24 | PX | | C | 0-0 | 23-19-11 | D09064J | 6 | | | D09063P | =CC | D | | 150, 152-199 |
| 906W | 24 | PX | | C | 20-2 | 23-19-11 | D09064J | 4 | | | D09063P | K- | | | 150, 152-199 |
| 906Z | | | | C | 0-0 | 23-19-11 | D09064J | DED | | | D09063P | =CC | D | | 150, 152-199 |

WIRE LIST
D280T132

91-21-11
Section W9040
Page 2
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|--------|--------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W9047 | 286T9047 | | | AIR GROUND PUBLIC TELEPHONE - CONTROL & TEST/SERVICE (continued) | | | | | | | | | | | | |
| 907 | 24 | PV | D | 20-2 | 23-19-11 | D09064J | 1 | | | D09063P | N- | | | | 150, 152-199 | |
| 907Z | | | D | 0-0 | 23-19-11 | D09064J | 15 | | | D09063P | P- | | | | 150, 152-199 | |
| W9048 | 286T9048 | | | AIR TO GROUND PUBLIC TELEPHONE -AIR/GND RELAY | | | | | | | | | | | | |
| 900 | 24 | PK | | 5-0 | 23-19-11 | D03554 | 3 | | | D04906J | 11 | | | | 150, 152-199 | |
| 901 | 24 | PK | | 5-0 | 23-19-11 | D03554 | 5 | | | D04906J | 32 | | | | 150, 152-199 | |
| W9049 | 286T9049 | | | AIR TO GROUND PUBLIC TELEPHONE - CTU TO ZTB-B | | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09066P | F | | | D09068P | 10 | | | | 150, 152-199 | |
| 901R | 26 | BW | A | 10-0 | 23-19-11 | D09066P | E | | | D09068P | 9 | | | | 150, 152-199 | |
| 901Z | | | A | 0-0 | 23-19-11 | D09066P | | | FA | D09068P | | | FB | | 150, 152-199 | |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09066P | D | | | D09068P | 2 | | | | 150, 152-199 | |
| 902Y | 26 | BW | B | 10-0 | 23-19-11 | D09066P | C | | | D09068P | 1 | | | | 150, 152-199 | |
| 902Z | | | B | 0-0 | 23-19-11 | D09066P | | | FA | D09068P | | | FB | | 150, 152-199 | |
| 903GY | 26 | BW | C | 10-0 | 23-19-11 | D09066P | A | | | D09068P | 12 | | | | 150, 152-199 | |
| 903W | 26 | BW | C | 0-0 | 23-19-11 | D09066P | B | | | D09068P | 14 | | | | 150, 152-199 | |
| 903Z | | | C | 0-0 | 23-19-11 | D09066P | | | FC | D09068P | | | FD | | 150, 152-199 | |
| 904B | 18 | Q5 | D | 0-0 | 23-19-11 | D09066P | M | | | D09068P | 13 | | | | 150, 152-199 | |
| 904BK | 18 | Q5 | D | 0-0 | 23-19-11 | D09066P | L | | | D09068P | 11 | | | | 150, 152-199 | |
| 904G | 18 | Q5 | D | 0-0 | 23-19-11 | D09066P | J | | | D09068P | 4 | | | | 150, 152-199 | |
| 904R | 18 | Q5 | D | 10-0 | 23-19-11 | D09066P | K | | | D09068P | 6 | | | | 150, 152-199 | |
| 904Z | | | D | 0-0 | 23-19-11 | D09066P | | | FC | D09068P | | | FD | | 150, 152-199 | |
| FRA | | | | 0-0 | 23-19-11 | D09066P | H | | | D09068P | | | FA | | 150, 152-199 | |
| FRB | | | | 0-0 | 23-19-11 | D09068P | 3 | | | D09068P | | | FB | | 150, 152-199 | |
| FRC | | | | 0-0 | 23-19-11 | D09066P | G | | | D09066P | | | FC | | 150, 152-199 | |
| FRD | | | | 0-0 | 23-19-11 | D09068P | 8 | | | D09068P | | | FD | | 150, 152-199 | |
| YAA | | | | 0-0 | 23-19-11 | D09066P | =CC | D | | D09068P | =CC | D | | | 150, 152-199 | |

WIRE LIST

D280T132

91-21-11

Section W9040

Page 3 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9050 | 286T9050 | | | AIR GROUND PUBLIC TELEPHONE - CTU TO ZTB-C | | | | | | | | | | | |
| 901B | 26 | BW | A | | 34-6 | 23-19-11 | D09067P | | F | | D09069P | | 10 | | 150, 152-199 |
| 901R | 26 | BW | A | | 0-0 | 23-19-11 | D09067P | | E | | D09069P | | 9 | | 150, 152-199 |
| 901Z | | | A | | 0-0 | 23-19-11 | D09067P | | | FA | D09069P | | | FB | 150, 152-199 |
| 902G | 26 | BW | B | | 34-6 | 23-19-11 | D09067P | | D | | D09069P | | 2 | | 150, 152-199 |
| 902Y | 26 | BW | B | | 0-0 | 23-19-11 | D09067P | | C | | D09069P | | 1 | | 150, 152-199 |
| 902Z | | | B | | 0-0 | 23-19-11 | D09067P | | | FA | D09069P | | | FB | 150, 152-199 |
| 903GY | 26 | BW | C | | 34-6 | 23-19-11 | D09067P | | A | | D09069P | | 12 | | 150, 152-199 |
| 903W | 26 | BW | C | | 0-0 | 23-19-11 | D09067P | | B | | D09069P | | 14 | | 150, 152-199 |
| 903Z | | | C | | 0-0 | 23-19-11 | D09067P | | | FC | D09069P | | | FD | 150, 152-199 |
| 904B | 18 | Q5 | D | | 0-0 | 23-19-11 | D09067P | | M | | D09069P | | 13 | | 150, 152-199 |
| 904BK | 18 | Q5 | D | | 0-0 | 23-19-11 | D09067P | | L | | D09069P | | 11 | | 150, 152-199 |
| 904G | 18 | Q5 | D | | 0-0 | 23-19-11 | D09067P | | J | | D09069P | | 4 | | 150, 152-199 |
| 904R | 18 | Q5 | D | | 34-6 | 23-19-11 | D09067P | | K | | D09069P | | 6 | | 150, 152-199 |
| 904Z | | | D | | 0-0 | 23-19-11 | D09067P | | | FC | D09069P | | | FD | 150, 152-199 |
| FRA | | | | | 0-0 | 23-19-11 | D09067P | | H | | D09067P | | | FA | 150, 152-199 |
| FRB | | | | | 0-0 | 23-19-11 | D09069P | | 3 | | D09069P | | | FB | 150, 152-199 |
| FRC | | | | | 0-0 | 23-19-11 | D09067P | | G | | D09067P | | | FC | 150, 152-199 |
| FRD | | | | | 0-0 | 23-19-11 | D09069P | | 8 | | D09069P | | | FD | 150, 152-199 |
| YAA | | | | | 0-0 | 23-19-11 | D09067P | | =CC | D | D09069P | | =CC | D | 150, 152-199 |
| W9051 | 286T9051 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-B TO STB LOOP 0 | | | | | | | | | | | |
| 901B | 26 | BW | A | | 24-5 | 23-19-11 | D09070P | | 13 | | D09073J | | 13 | | 150, 152-199 |
| 901R | 26 | BW | A | | 0-0 | 23-19-11 | D09070P | | 5 | | D09073J | | 5 | | 150, 152-199 |
| 901Z | | | A | | 0-0 | 23-19-11 | D09070P | | 12 | | D09073J | | 12 | | 150, 152-199 |
| 902G | 26 | BW | B | | 0-0 | 23-19-11 | D09070P | | 11 | | D09073J | | 11 | | 150, 152-199 |
| 902Y | 26 | BW | B | | 24-5 | 23-19-11 | D09070P | | 4 | | D09073J | | 4 | | 150, 152-199 |
| 902Z | | | B | | 0-0 | 23-19-11 | D09070P | | 3 | | D09073J | | 3 | | 150, 152-199 |
| 903GY | 26 | BW | C | | 24-5 | 23-19-11 | D09070P | | 7 | | D09073J | | 7 | | 150, 152-199 |
| 903W | 26 | BW | C | | 0-0 | 23-19-11 | D09070P | | 15 | | D09073J | | 15 | | 150, 152-199 |
| 903Z | | | C | | 0-0 | 23-19-11 | D09070P | | 14 | | D09073J | | 14 | | 150, 152-199 |
| 904B | 18 | PA | | | 24-5 | 23-19-11 | D09070P | | 2 | | D09073J | | 2 | | 150, 152-199 |
| 904G | 18 | PA | | | 24-5 | 23-19-11 | D09070P | | 9 | | D09073J | | 9 | | 150, 152-199 |
| 904R | 18 | PA | | | 24-5 | 23-19-11 | D09070P | | 1 | | D09073J | | 1 | | 150, 152-199 |
| YAA | | | | | 10-0 | 23-19-11 | D09070P | | =CC | D | D09073J | | =CC | D | 150, 152-199 |
| W9052 | 286T9052 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-B TO STB LOOP 1 | | | | | | | | | | | |
| 901B | 26 | BW | A | | 0-0 | 23-19-11 | D09071P | | 13 | | D09074J | | 13 | | 150, 152-199 |
| 901R | 26 | BW | A | | 13-0 | 23-19-11 | D09071P | | 5 | | D09074J | | 5 | | 150, 152-199 |
| 901Z | | | A | | 0-0 | 23-19-11 | D09071P | | 12 | | D09074J | | 12 | | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W9050

Page 1

Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|--------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W9052 | 286T9052 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-B TO STB LOOP 1 (continued) | | | | | | | | | | | | |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09071P | 11 | | | | D09074J | 11 | | | 150, 152-199 | |
| 902Y | 26 | BW | B | 13-0 | 23-19-11 | D09071P | 4 | | | | D09074J | 4 | | | 150, 152-199 | |
| 902Z | | | B | 0-0 | 23-19-11 | D09071P | 3 | | | | D09074J | 3 | | | 150, 152-199 | |
| 903GY | 26 | BW | C | 13-0 | 23-19-11 | D09071P | 7 | | | | D09074J | 7 | | | 150, 152-199 | |
| 903W | 26 | BW | C | 0-0 | 23-19-11 | D09071P | 15 | | | | D09074J | 15 | | | 150, 152-199 | |
| 903Z | | | C | 0-0 | 23-19-11 | D09071P | 14 | | | | D09074J | 14 | | | 150, 152-199 | |
| 904B | 18 | PA | | 13-0 | 23-19-11 | D09071P | 2 | | | | D09074J | 2 | | | 150, 152-199 | |
| 904G | 18 | PA | | 13-0 | 23-19-11 | D09071P | 9 | | | | D09074J | 9 | | | 150, 152-199 | |
| 904R | 18 | PA | | 13-0 | 23-19-11 | D09071P | 1 | | | | D09074J | 1 | | | 150, 152-199 | |
| YAA | | | | 0-0 | 23-19-11 | D09071P | | =CC | D | | D09074J | | =CC | D | 150, 152-199 | |
| W9053 | 286T9053 | | | AIR TO GROUND PULBIC TELEPHONE - ZTB-B TO STB LOOP 2 | | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09072P | 13 | | | | D09075J | 13 | | | 150, 152-199 | |
| 901R | 26 | BW | A | 15-11 | 23-19-11 | D09072P | 5 | | | | D09075J | 5 | | | 150, 152-199 | |
| 901Z | | | A | 0-0 | 23-19-11 | D09072P | 12 | | | | D09075J | 12 | | | 150, 152-199 | |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09072P | 11 | | | | D09075J | 11 | | | 150, 152-199 | |
| 902Y | 26 | BW | B | 15-11 | 23-19-11 | D09072P | 4 | | | | D09075J | 4 | | | 150, 152-199 | |
| 902Z | | | B | 0-0 | 23-19-11 | D09072P | 3 | | | | D09075J | 3 | | | 150, 152-199 | |
| 903GY | 26 | BW | C | 0-0 | 23-19-11 | D09072P | 7 | | | | D09075J | 7 | | | 150, 152-199 | |
| 903W | 26 | BW | C | 15-11 | 23-19-11 | D09072P | 15 | | | | D09075J | 15 | | | 150, 152-199 | |
| 903Z | | | C | 0-0 | 23-19-11 | D09072P | 14 | | | | D09075J | 14 | | | 150, 152-199 | |
| 904B | 18 | PA | | 15-11 | 23-19-11 | D09072P | 2 | | | | D09075J | 2 | | | 150, 152-199 | |
| 904G | 18 | PA | | 15-11 | 23-19-11 | D09072P | 9 | | | | D09075J | 9 | | | 150, 152-199 | |
| 904R | 18 | PA | | 15-11 | 23-19-11 | D09072P | 1 | | | | D09075J | 1 | | | 150, 152-199 | |
| YAA | | | | 0-0 | 23-19-11 | D09072P | | =CC | D | | D09075J | | =CC | D | 150, 152-199 | |
| W9054 | 286T9054 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-C TO STB LOOP 0 | | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09076P | 13 | | | | D09079J | 13 | | | 150, 152-199 | |
| 901R | 26 | BW | A | 20-4 | 23-19-11 | D09076P | 5 | | | | D09079J | 5 | | | 150, 152-199 | |
| 901Z | | | A | 0-0 | 23-19-11 | D09076P | 12 | | | | D09079J | 12 | | | 150, 152-199 | |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09076P | 11 | | | | D09079J | 11 | | | 150, 152-199 | |
| 902Y | 26 | BW | B | 20-4 | 23-19-11 | D09076P | 4 | | | | D09079J | 4 | | | 150, 152-199 | |
| 902Z | | | B | 0-0 | 23-19-11 | D09076P | 3 | | | | D09079J | 3 | | | 150, 152-199 | |
| 903GY | 26 | BW | C | 20-4 | 23-19-11 | D09076P | 7 | | | | D09079J | 7 | | | 150, 152-199 | |
| 903W | 26 | BW | C | 0-0 | 23-19-11 | D09076P | 15 | | | | D09079J | 15 | | | 150, 152-199 | |
| 903Z | | | C | 0-0 | 23-19-11 | D09076P | 14 | | | | D09079J | 14 | | | 150, 152-199 | |
| 904B | 18 | PA | | 20-4 | 23-19-11 | D09076P | 2 | | | | D09079J | 2 | | | 150, 152-199 | |
| 904G | 18 | PA | | 20-4 | 23-19-11 | D09076P | 9 | | | | D09079J | 9 | | | 150, 152-199 | |
| 904R | 18 | PA | | 20-4 | 23-19-11 | D09076P | 1 | | | | D09079J | 1 | | | 150, 152-199 | |

WIRE LIST

D280T132

91-21-11

Section W9050

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|--------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9054 | 286T9054 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-C TO STB LOOP 0 (continued) | | | | | | | | | | | |
| YAA | | | | 10-0 | 23-19-11 | D09076P | =CC | D | | D09079J | =CC | D | | 150, 152-199 | |
| W9055 | 286T9055 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-C TO STB LOOP 1 | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09077P | | 13 | | D09080J | | 13 | | 150, 152-199 | |
| 901R | 26 | BW | A | 15-11 | 23-19-11 | D09077P | | 5 | | D09080J | | 5 | | 150, 152-199 | |
| 901Z | | | A | 0-0 | 23-19-11 | D09077P | | 12 | | D09080J | | 12 | | 150, 152-199 | |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09077P | | 11 | | D09080J | | 11 | | 150, 152-199 | |
| 902Y | 26 | BW | B | 15-11 | 23-19-11 | D09077P | | 4 | | D09080J | | 4 | | 150, 152-199 | |
| 902Z | | | B | 0-0 | 23-19-11 | D09077P | | 3 | | D09080J | | 3 | | 150, 152-199 | |
| 903GY | 26 | BW | C | 15-11 | 23-19-11 | D09077P | | 7 | | D09080J | | 7 | | 150, 152-199 | |
| 903W | 26 | BW | C | 0-0 | 23-19-11 | D09077P | | 15 | | D09080J | | 15 | | 150, 152-199 | |
| 903Z | | | C | 0-0 | 23-19-11 | D09077P | | 14 | | D09080J | | 14 | | 150, 152-199 | |
| 904B | 18 | PA | | 15-11 | 23-19-11 | D09077P | | 2 | | D09080J | | 2 | | 150, 152-199 | |
| 904G | 18 | PA | | 15-11 | 23-19-11 | D09077P | | 9 | | D09080J | | 9 | | 150, 152-199 | |
| 904R | 18 | PA | | 15-11 | 23-19-11 | D09077P | | 1 | | D09080J | | 1 | | 150, 152-199 | |
| YAA | | | | 0-0 | 23-19-11 | D09077P | =CC | D | | D09080J | =CC | D | | 150, 152-199 | |
| W9056 | 286T9056 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-C TO STB LOOP 2 | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09078P | | 13 | | D09081J | | 13 | | 150, 152-199 | |
| 901R | 26 | BW | A | 11-10 | 23-19-11 | D09078P | | 5 | | D09081J | | 5 | | 150, 152-199 | |
| 901Z | | | A | 0-0 | 23-19-11 | D09078P | | 12 | | D09081J | | 12 | | 150, 152-199 | |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09078P | | 11 | | D09081J | | 11 | | 150, 152-199 | |
| 902Y | 26 | BW | B | 11-10 | 23-19-11 | D09078P | | 4 | | D09081J | | 4 | | 150, 152-199 | |
| 902Z | | | B | 0-0 | 23-19-11 | D09078P | | 3 | | D09081J | | 3 | | 150, 152-199 | |
| 903GY | 26 | BW | C | 11-10 | 23-19-11 | D09078P | | 7 | | D09081J | | 7 | | 150, 152-199 | |
| 903W | 26 | BW | C | 0-0 | 23-19-11 | D09078P | | 15 | | D09081J | | 15 | | 150, 152-199 | |
| 903Z | | | C | 0-0 | 23-19-11 | D09078P | | 14 | | D09081J | | 14 | | 150, 152-199 | |
| 904B | 18 | PA | | 11-10 | 23-19-11 | D09078P | | 2 | | D09081J | | 2 | | 150, 152-199 | |
| 904G | 18 | PA | | 11-10 | 23-19-11 | D09078P | | 9 | | D09081J | | 9 | | 150, 152-199 | |
| 904R | 18 | PA | | 11-10 | 23-19-11 | D09078P | | 1 | | D09081J | | 1 | | 150, 152-199 | |
| YAA | | | | 0-0 | 23-19-11 | D09078P | =CC | D | | D09081J | =CC | D | | 150, 152-199 | |
| W9057 | 286T9057 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-B TO STB LOOP 3 | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09083P | | 13 | | D09084P | | 13 | | 150, 152-199 | |
| 901R | 26 | BW | A | 28-5 | 23-19-11 | D09083P | | 5 | | D09084P | | 5 | | 150, 152-199 | |
| 901Z | | | A | 0-0 | 23-19-11 | D09083P | | 12 | | D09084P | | 12 | | 150, 152-199 | |
| 902G | 26 | BW | B | 28-5 | 23-19-11 | D09083P | | 11 | | D09084P | | 11 | | 150, 152-199 | |
| 902Y | 26 | BW | B | 0-0 | 23-19-11 | D09083P | | 4 | | D09084P | | 4 | | 150, 152-199 | |

WIRE LIST

D280T132

91-21-11
Section W9050
Page 3
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | |
|--------------|-----------------|----|-------|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9057 | 286T9057 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-B TO STB LOOP 3 (continued) | | | | | | | | | | | |
| 902Z | | | B | 0-0 | 23-19-11 | D09083P | | 3 | | | D09084P | | 3 | | 150, 152-199 |
| 903GY | 26 | BW | C | 28-5 | 23-19-11 | D09083P | | 7 | | | D09084P | | 7 | | 150, 152-199 |
| 903W | 26 | BW | C | 0-0 | 23-19-11 | D09083P | | 15 | | | D09084P | | 15 | | 150, 152-199 |
| 903Z | | | C | 0-0 | 23-19-11 | D09083P | | 14 | | | D09084P | | 14 | | 150, 152-199 |
| 904B | 18 | PA | | 28-5 | 23-19-11 | D09083P | | 2 | | | D09084P | | 2 | | 150, 152-199 |
| 904G | 18 | PA | | 28-5 | 23-19-11 | D09083P | | 9 | | | D09084P | | 9 | | 150, 152-199 |
| 904R | 18 | PA | | 28-5 | 23-19-11 | D09083P | | 1 | | | D09084P | | 1 | | 150, 152-199 |
| YAA | | | | 0-0 | 23-19-11 | D09083P | =CC | | D | | D09084P | =CC | | D | 150, 152-199 |
| W9058 | 286T9058 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB TO STB LOOP 3 | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09085P | | 13 | | | D09086P | | 13 | | 150, 152-199 |
| 901R | 26 | BW | A | 21-2 | 23-19-11 | D09085P | | 5 | | | D09086P | | 5 | | 150, 152-199 |
| 901Z | | | A | 0-0 | 23-19-11 | D09085P | | 12 | | | D09086P | | 12 | | 150, 152-199 |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09085P | | 11 | | | D09086P | | 11 | | 150, 152-199 |
| 902Y | 26 | BW | B | 21-2 | 23-19-11 | D09085P | | 4 | | | D09086P | | 4 | | 150, 152-199 |
| 902Z | | | B | 0-0 | 23-19-11 | D09085P | | 3 | | | D09086P | | 3 | | 150, 152-199 |
| 903B | 18 | PA | | 21-2 | 23-19-11 | D09085P | | 2 | | | D09086P | | 2 | | 150, 152-199 |
| 903G | 18 | PA | | 21-2 | 23-19-11 | D09085P | | 9 | | | D09086P | | 9 | | 150, 152-199 |
| 903R | 18 | PA | | 21-2 | 23-19-11 | D09085P | | 1 | | | D09086P | | 1 | | 150, 152-199 |
| YAA | | | | 0-0 | 23-19-11 | D09085P | =CC | | D | | D09086P | =CC | | D | 150, 152-199 |
| W9059 | 286T9059 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-B TO STB LOOP 0 | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09073P | | 13 | | | D09102P | | 13 | | 150, 152-199 |
| 901R | 26 | BW | A | 10-0 | 23-19-11 | D09073P | | 5 | | | D09102P | | 5 | | 150, 152-199 |
| 901Z | | | A | 0-0 | 23-19-11 | D09073P | | 12 | | | D09102P | | 12 | | 150, 152-199 |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09073P | | 11 | | | D09102P | | 11 | | 150, 152-199 |
| 902Y | 26 | BW | B | 10-0 | 23-19-11 | D09073P | | 4 | | | D09102P | | 4 | | 150, 152-199 |
| 902Z | | | B | 0-0 | 23-19-11 | D09073P | | 3 | | | D09102P | | 3 | | 150, 152-199 |
| 903B | 18 | PA | | 10-0 | 23-19-11 | D09073P | | 2 | | | D09102P | | 2 | | 150, 152-199 |
| 903G | 18 | PA | | 10-0 | 23-19-11 | D09073P | | 9 | | | D09102P | | 9 | | 150, 152-199 |
| 903R | 18 | PA | | 10-0 | 23-19-11 | D09073P | | 1 | | | D09102P | | 1 | | 150, 152-199 |
| YAA | | | | 0-0 | 23-19-11 | D09073P | =CC | | D | | D09102P | =CC | | D | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W9050

Page 4 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|--------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9060 | 286T9060 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-B TO STB LOOP 1 | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09074P | 13 | | | D09102P | 13 | | | 150, 152-199 | |
| 901R | 26 | BW | A | 10-0 | 23-19-11 | D09074P | 5 | | | D09102P | 5 | | | 150, 152-199 | |
| 901Z | | | A | 0-0 | 23-19-11 | D09074P | 12 | | | D09102P | 12 | | | 150, 152-199 | |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09074P | 11 | | | D09102P | 11 | | | 150, 152-199 | |
| 902Y | 26 | BW | B | 10-0 | 23-19-11 | D09074P | 4 | | | D09102P | 4 | | | 150, 152-199 | |
| 902Z | | | B | 0-0 | 23-19-11 | D09074P | 3 | | | D09102P | 3 | | | 150, 152-199 | |
| 903B | 18 | PA | | 10-0 | 23-19-11 | D09074P | 2 | | | D09102P | 2 | | | 150, 152-199 | |
| 903G | 18 | PA | | 10-0 | 23-19-11 | D09074P | 9 | | | D09102P | 9 | | | 150, 152-199 | |
| 903R | 18 | PA | | 10-0 | 23-19-11 | D09074P | 1 | | | D09102P | 1 | | | 150, 152-199 | |
| YAA | | | | 0-0 | 23-19-11 | D09074P | =CC | D | | D09102P | =CC | D | | 150, 152-199 | |
| W9061 | 286T9061 | | | AIR GROUND PUBLIC TELEPHONE - ZTB-B TO STB LOOP 2 | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09075P | 13 | | | D09102P | 13 | | | 150, 152-199 | |
| 901R | 26 | BW | A | 10-0 | 23-19-11 | D09075P | 5 | | | D09102P | 5 | | | 150, 152-199 | |
| 901Z | | | A | 0-0 | 23-19-11 | D09075P | 12 | | | D09102P | 12 | | | 150, 152-199 | |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09075P | 11 | | | D09102P | 11 | | | 150, 152-199 | |
| 902Y | 26 | BW | B | 10-0 | 23-19-11 | D09075P | 4 | | | D09102P | 4 | | | 150, 152-199 | |
| 902Z | | | B | 0-0 | 23-19-11 | D09075P | 3 | | | D09102P | 3 | | | 150, 152-199 | |
| 903B | 18 | PA | | 10-0 | 23-19-11 | D09075P | 2 | | | D09102P | 2 | | | 150, 152-199 | |
| 903G | 18 | PA | | 10-0 | 23-19-11 | D09075P | 9 | | | D09102P | 9 | | | 150, 152-199 | |
| 903R | 18 | PA | | 10-0 | 23-19-11 | D09075P | 1 | | | D09102P | 1 | | | 150, 152-199 | |
| YAA | | | | 0-0 | 23-19-11 | D09075P | =CC | D | | D09102P | =CC | D | | 150, 152-199 | |
| W9062 | 286T9062 | | | AIR TO GROUND PUBLIC TELEPHONE - STB TO STB | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09101P | 13 | | | D09102P | 13 | | | 150, 152-199 | |
| 901R | 26 | BW | A | 10-0 | 23-19-11 | D09101P | 5 | | | D09102P | 5 | | | 150, 152-199 | |
| 901Z | | | A | 0-0 | 23-19-11 | D09101P | 12 | | | D09102P | 12 | | | 150, 152-199 | |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09101P | 11 | | | D09102P | 11 | | | 150, 152-199 | |
| 902Y | 26 | BW | B | 10-0 | 23-19-11 | D09101P | 4 | | | D09102P | 4 | | | 150, 152-199 | |
| 902Z | | | B | 0-0 | 23-19-11 | D09101P | 3 | | | D09102P | 3 | | | 150, 152-199 | |
| 903B | 18 | PA | | 10-0 | 23-19-11 | D09101P | 2 | | | D09102P | 2 | | | 150, 152-199 | |
| 903G | 18 | PA | | 10-0 | 23-19-11 | D09101P | 9 | | | D09102P | 9 | | | 150, 152-199 | |
| 903R | 18 | PA | | 10-0 | 23-19-11 | D09101P | 1 | | | D09102P | 1 | | | 150, 152-199 | |
| YAA | | | | 0-0 | 23-19-11 | D09101P | =CC | D | | D09102P | =CC | D | | 150, 152-199 | |
| W9063 | 286T9063 | | | AIR TO GROUND PUBLIC TELEPHONE - STB TO STB - ZTB-C LOOP 3 | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09101P | 13 | | | D09102P | 13 | | | 150, 152-199 | |
| 901R | 26 | BW | A | 10-0 | 23-19-11 | D09101P | 5 | | | D09102P | 5 | | | 150, 152-199 | |

WIRE LIST
D280T132

91-21-11
Section W9060
Page 1
Mar 09/2006



| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|--------|---------|------|------|--------|--|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W9063 | 286T9063 | | | AIR TO GROUND PUBLIC TELEPHONE - STB TO STB - ZTB-C LOOP 3 (continued) | | | | | | | | | | | | |
| 901Z | | | A | 0-0 | 23-19-11 | D09101P | | 12 | | | D09102P | | 12 | | | 150, 152-199 |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09101P | | 11 | | | D09102P | | 11 | | | 150, 152-199 |
| 902Y | 26 | BW | B | 10-0 | 23-19-11 | D09101P | | 4 | | | D09102P | | 4 | | | 150, 152-199 |
| 902Z | | | B | 0-0 | 23-19-11 | D09101P | | 3 | | | D09102P | | 3 | | | 150, 152-199 |
| 903B | 18 | PA | | 10-0 | 23-19-11 | D09101P | | 2 | | | D09102P | | 2 | | | 150, 152-199 |
| 903G | 18 | PA | | 10-0 | 23-19-11 | D09101P | | 9 | | | D09102P | | 9 | | | 150, 152-199 |
| 903R | 18 | PA | | 10-0 | 23-19-11 | D09101P | | 1 | | | D09102P | | 1 | | | 150, 152-199 |
| YAA | | | | 0-0 | 23-19-11 | D09101P | =CC | D | | | D09102P | =CC | D | | | 150, 152-199 |
| W9064 | 286T9064 | | | AIR TO GROUND PUBLIC TELEPHONE - STB TO STB | | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09101P | | 13 | | | D09102P | | 13 | | | 150, 152-199 |
| 901R | 26 | BW | A | 10-0 | 23-19-11 | D09101P | | 5 | | | D09102P | | 5 | | | 150, 152-199 |
| 901Z | | | A | 0-0 | 23-19-11 | D09101P | | 12 | | | D09102P | | 12 | | | 150, 152-199 |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09101P | | 11 | | | D09102P | | 11 | | | 150, 152-199 |
| 902Y | 26 | BW | B | 10-0 | 23-19-11 | D09101P | | 4 | | | D09102P | | 4 | | | 150, 152-199 |
| 902Z | | | B | 0-0 | 23-19-11 | D09101P | | 3 | | | D09102P | | 3 | | | 150, 152-199 |
| 903B | 18 | PA | | 10-0 | 23-19-11 | D09101P | | 2 | | | D09102P | | 2 | | | 150, 152-199 |
| 903G | 18 | PA | | 10-0 | 23-19-11 | D09101P | | 9 | | | D09102P | | 9 | | | 150, 152-199 |
| 903R | 18 | PA | | 10-0 | 23-19-11 | D09101P | | 1 | | | D09102P | | 1 | | | 150, 152-199 |
| YAA | | | | 0-0 | 23-19-11 | D09101P | =CC | D | | | D09102P | =CC | D | | | 150, 152-199 |
| W9065 | 286T9065 | | | AIR TO GROUND PUBLIC TELEPHONE - STB TO STB - ZTB-C LOOP3 | | | | | | | | | | | | |
| 901B | 26 | BW | A | 10-0 | 23-19-11 | D09101P | | 13 | | | D09102P | | 13 | | | 150, 152-199 |
| 901R | 26 | BW | A | 0-0 | 23-19-11 | D09101P | | 5 | | | D09102P | | 5 | | | 150, 152-199 |
| 901Z | | | A | 0-0 | 23-19-11 | D09101P | | 12 | | | D09102P | | 12 | | | 150, 152-199 |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09101P | | 11 | | | D09102P | | 11 | | | 150, 152-199 |
| 902Y | 26 | BW | B | 10-0 | 23-19-11 | D09101P | | 4 | | | D09102P | | 4 | | | 150, 152-199 |
| 902Z | | | B | 0-0 | 23-19-11 | D09101P | | 3 | | | D09102P | | 3 | | | 150, 152-199 |
| 903B | 18 | PA | | 10-0 | 23-19-11 | D09101P | | 2 | | | D09102P | | 2 | | | 150, 152-199 |
| 903G | 18 | PA | | 10-0 | 23-19-11 | D09101P | | 9 | | | D09102P | | 9 | | | 150, 152-199 |
| 903R | 18 | PA | | 10-0 | 23-19-11 | D09101P | | 1 | | | D09102P | | 1 | | | 150, 152-199 |
| YAA | | | | 0-0 | 23-19-11 | D09101P | =CC | D | | | D09102P | =CC | D | | | 150, 152-199 |
| W9067 | 286T9067 | | | AIR TO GROUND PUBLIC TELEPHONE - STB TO STB - ZTB-C LOOP 3 | | | | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09101P | | 13 | | | D09102P | | 13 | | | 150, 152-199 |
| 901R | 26 | BW | A | 53-5 | 23-19-11 | D09101P | | 5 | | | D09102P | | 5 | | | 150, 152-199 |
| 901Z | | | A | 0-0 | 23-19-11 | D09101P | | 12 | | | D09102P | | 12 | | | 150, 152-199 |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09101P | | 11 | | | D09102P | | 11 | | | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W9060

Page 2

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | Effectivity |
|------------------------|-----------------|----|----|-------|---|---------|-------|------|------|---------|-------|------|------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | |
| W9067 | 286T9067 | | | | AIR TO GROUND PUBLIC TELEPHONE - STB TO STB - ZTB-C LOOP 3 (continued) | | | | | | | | | |
| 902Y | 26 | BW | B | 53-5 | 23-19-11 | D09101P | 4 | | | D09102P | 4 | | | 150, 152-199 |
| 902Z | | | B | 0-0 | 23-19-11 | D09101P | 3 | | | D09102P | 3 | | | 150, 152-199 |
| 903B | 18 | PA | | 53-5 | 23-19-11 | D09101P | 2 | | | D09102P | 2 | | | 150, 152-199 |
| 903G | 18 | PA | | 53-5 | 23-19-11 | D09101P | 9 | | | D09102P | 9 | | | 150, 152-199 |
| 903R | 18 | PA | | 53-5 | 23-19-11 | D09101P | 1 | | | D09102P | 1 | | | 150, 152-199 |
| YAA | | | | 0-0 | 23-19-11 | D09101P | =CC | D | | D09102P | =CC | D | | 150, 152-199 |
| W9068 | 286T9068 | | | | AIR TO GROUND PUBLIC TELEPHONE - STB TO STB - ZTB-C LOOP 3 | | | | | | | | | |
| 901B | 26 | BW | A | 0-0 | 23-19-11 | D09101P | 13 | | | D09102P | 13 | | | 150, 152-199 |
| 901R | 26 | BW | A | 39-10 | 23-19-11 | D09101P | 5 | | | D09102P | 5 | | | 150, 152-199 |
| 901Z | | | A | 0-0 | 23-19-11 | D09101P | 12 | | | D09102P | 12 | | | 150, 152-199 |
| 902G | 26 | BW | B | 0-0 | 23-19-11 | D09101P | 11 | | | D09102P | 11 | | | 150, 152-199 |
| 902Y | 26 | BW | B | 39-10 | 23-19-11 | D09101P | 4 | | | D09102P | 4 | | | 150, 152-199 |
| 902Z | | | B | 0-0 | 23-19-11 | D09101P | 3 | | | D09102P | 3 | | | 150, 152-199 |
| 903B | 18 | PA | | 39-10 | 23-19-11 | D09101P | 2 | | | D09102P | 2 | | | 150, 152-199 |
| 903G | 18 | PA | | 39-10 | 23-19-11 | D09101P | 9 | | | D09102P | 9 | | | 150, 152-199 |
| 903R | 18 | PA | | 39-10 | 23-19-11 | D09101P | 1 | | | D09102P | 1 | | | 150, 152-199 |
| YAA | | | | 0-0 | 23-19-11 | D09101P | =CC | D | | D09102P | =CC | D | | 150, 152-199 |
| W9069 | 286T9069 | | | | PASSENGER TELEPHONE RIGHT SIDE OBSERVERS PANEL - CTU ON/OFF | | | | | | | | | |
| 900 | 24 | PK | | 5-0 | 23-19-11 | D09110J | 1 | | | S09011 | 2 | E | | 150, 152-199 |
| 901 | 24 | PK | | 5-0 | 23-19-11 | D09110J | 2 | | | S09011 | 3 | E | | 150, 152-199 |

WIRE LIST
D280T132

91-21-11
Section W9060
Page 3 End
Mar 09/2006



| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9071 | 286T9071 | | | HANDSET TO STB CONNECTION | | | | | | | | | | | |
| 901BK | 24 | | PM | AA | 10-0 | 23-19-11 | D09104J | | 5 | | D09103 | | 1 | | 150, 152-199 |
| 901R | 24 | | PM | AA | 0-0 | 23-19-11 | D09104J | | 4 | | D09103 | | 9 | | 150, 152-199 |
| 901W | 24 | | PM | AA | 0-0 | 23-19-11 | D09104J | | 3 | | D09103 | | 2 | | 150, 152-199 |
| 902G | 24 | | PK | | 10-0 | 23-19-11 | D09104J | | 6 | | D09103 | | 10 | | 150, 152-199 |
| 903BR | 24 | | PM | AB | 10-0 | 23-19-11 | D09104J | | 7 | | D09103 | | 3 | | 150, 152-199 |
| 903GY | 24 | | PM | AB | 0-0 | 23-19-11 | D09104J | | 9 | | D09103 | | 11 | | 150, 152-199 |
| 903Y | 24 | | PM | AB | 0-0 | 23-19-11 | D09104J | | 8 | | D09103 | | 4 | | 150, 152-199 |
| 904B | 24 | | PL | AC | 10-0 | 23-19-11 | D09104J | | 2 | | D09103 | | 5 | | 150, 152-199 |
| 904O | 24 | | PL | AC | 0-0 | 23-19-11 | D09104J | | 1 | | D09103 | | 12 | | 150, 152-199 |
| W9072 | 286T9072 | | | HANDSET TO STB CONNECTION | | | | | | | | | | | |
| 901BK | 24 | | PM | AA | 4-6 | 23-19-11 | D09107 | | 2 | | D09109 | | 1 | | 150, 152-199 |
| 901R | 24 | | PM | AA | 0-0 | 23-19-11 | D09107 | | 1 | | D09109 | | 9 | | 150, 152-199 |
| 901W | 24 | | PM | AA | 0-0 | 23-19-11 | D09107 | | 4 | | D09109 | | 2 | | 150, 152-199 |
| 902G | 24 | | PK | | 4-6 | 23-19-11 | D09107 | | 3 | | D09109 | | 10 | | 150, 152-199 |
| 903BR | 24 | | PM | AB | 4-6 | 23-19-11 | D09107 | | 5 | | D09109 | | 3 | | 150, 152-199 |
| 903GY | 24 | | PM | AB | 0-0 | 23-19-11 | D09107 | | 7 | | D09109 | | 11 | | 150, 152-199 |
| 903Y | 24 | | PM | AB | 0-0 | 23-19-11 | D09107 | | 6 | | D09109 | | 4 | | 150, 152-199 |
| 904B | 24 | | PL | AC | 4-6 | 23-19-11 | D09108 | | 2 | | D09109 | | 5 | | 150, 152-199 |
| 904O | 24 | | PL | AC | 0-0 | 23-19-11 | D09108 | | 1 | | D09109 | | 12 | | 150, 152-199 |
| W9073 | 286T9073 | | | HANDSET TO STB CONNECTION | | | | | | | | | | | |
| 901BK | 24 | | PM | AA | 10-0 | 23-19-11 | D09105 | | 2 | | D09104P | | 5 | | 150, 152-199 |
| 901R | 24 | | PM | AA | 0-0 | 23-19-11 | D09105 | | 1 | | D09104P | | 4 | | 150, 152-199 |
| 901W | 24 | | PM | AA | 0-0 | 23-19-11 | D09105 | | 4 | | D09104P | | 3 | | 150, 152-199 |
| 902G | 24 | | PK | | 10-0 | 23-19-11 | D09105 | | 3 | | D09104P | | 6 | | 150, 152-199 |
| 903BR | 24 | | PM | AB | 10-0 | 23-19-11 | D09105 | | 5 | | D09104P | | 7 | | 150, 152-199 |
| 903GY | 24 | | PM | AB | 0-0 | 23-19-11 | D09105 | | 7 | | D09104P | | 9 | | 150, 152-199 |
| 903Y | 24 | | PM | AB | 0-0 | 23-19-11 | D09105 | | 6 | | D09104P | | 8 | | 150, 152-199 |
| 904B | 24 | | PL | AC | 10-0 | 23-19-11 | D09106 | | 2 | | D09104P | | 2 | | 150, 152-199 |
| 904O | 24 | | PL | AC | 0-0 | 23-19-11 | D09106 | | 1 | | D09104P | | 1 | | 150, 152-199 |
| W9074 | 286T9074 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-C TO STB LOOP 0 | | | | | | | | | | | |
| 901B | 26 | | BW | A | 0-0 | 23-19-11 | D09079P | | 13 | | D09102P | | 13 | | 150, 152-199 |
| 901R | 26 | | BW | A | 10-0 | 23-19-11 | D09079P | | 5 | | D09102P | | 5 | | 150, 152-199 |
| 901Z | | | | A | 0-0 | 23-19-11 | D09079P | | 12 | | D09102P | | 12 | | 150, 152-199 |
| 902G | 26 | | BW | B | 0-0 | 23-19-11 | D09079P | | 11 | | D09102P | | 11 | | 150, 152-199 |
| 902Y | 26 | | BW | B | 10-0 | 23-19-11 | D09079P | | 4 | | D09102P | | 4 | | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W9070

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9074 | 286T9074 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-C TO STB LOOP 0 (continued) | | | | | | | | | | | |
| 902Z | | | | B | 0-0 | 23-19-11 | D09079P | | 3 | | D09102P | | 3 | | 150, 152-199 |
| 903B | 18 | PA | | | 10-0 | 23-19-11 | D09079P | | 2 | | D09102P | | 2 | | 150, 152-199 |
| 903G | 18 | PA | | | 10-0 | 23-19-11 | D09079P | | 9 | | D09102P | | 9 | | 150, 152-199 |
| 903R | 18 | PA | | | 10-0 | 23-19-11 | D09079P | | 1 | | D09102P | | 1 | | 150, 152-199 |
| YAA | | | | | 0-0 | 23-19-11 | D09079P | =CC | D | | D09102P | =CC | D | | 150, 152-199 |
| W9075 | 286T9075 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-C TO STB LOOP 1 | | | | | | | | | | | |
| 901B | 26 | BW | A | | 0-0 | 23-19-11 | D09080P | | 13 | | D09102P | | 13 | | 150, 152-199 |
| 901R | 26 | BW | A | | 10-0 | 23-19-11 | D09080P | | 5 | | D09102P | | 5 | | 150, 152-199 |
| 901Z | | | A | | 0-0 | 23-19-11 | D09080P | | 12 | | D09102P | | 12 | | 150, 152-199 |
| 902G | 26 | BW | B | | 0-0 | 23-19-11 | D09080P | | 11 | | D09102P | | 11 | | 150, 152-199 |
| 902Y | 26 | BW | B | | 10-0 | 23-19-11 | D09080P | | 4 | | D09102P | | 4 | | 150, 152-199 |
| 902Z | | | B | | 0-0 | 23-19-11 | D09080P | | 3 | | D09102P | | 3 | | 150, 152-199 |
| 903B | 18 | PA | | | 10-0 | 23-19-11 | D09080P | | 2 | | D09102P | | 2 | | 150, 152-199 |
| 903G | 18 | PA | | | 10-0 | 23-19-11 | D09080P | | 9 | | D09102P | | 9 | | 150, 152-199 |
| 903R | 18 | PA | | | 10-0 | 23-19-11 | D09080P | | 1 | | D09102P | | 1 | | 150, 152-199 |
| YAA | | | | | 0-0 | 23-19-11 | D09080P | =CC | D | | D09102P | =CC | D | | 150, 152-199 |
| W9076 | 286T9076 | | | AIR TO GROUND PUBLIC TELEPHONE - ZTB-C TO STB LOOP 2 | | | | | | | | | | | |
| 901B | 26 | BW | A | | 0-0 | 23-19-11 | D09081P | | 13 | | D09102P | | 13 | | 150, 152-199 |
| 901R | 26 | BW | A | | 10-0 | 23-19-11 | D09081P | | 5 | | D09102P | | 5 | | 150, 152-199 |
| 901Z | | | A | | 0-0 | 23-19-11 | D09081P | | 12 | | D09102P | | 12 | | 150, 152-199 |
| 902G | 26 | BW | B | | 0-0 | 23-19-11 | D09081P | | 11 | | D09102P | | 11 | | 150, 152-199 |
| 902Y | 26 | BW | B | | 10-0 | 23-19-11 | D09081P | | 4 | | D09102P | | 4 | | 150, 152-199 |
| 902Z | | | B | | 0-0 | 23-19-11 | D09081P | | 3 | | D09102P | | 3 | | 150, 152-199 |
| 903B | 18 | PA | | | 10-0 | 23-19-11 | D09081P | | 2 | | D09102P | | 2 | | 150, 152-199 |
| 903G | 18 | PA | | | 10-0 | 23-19-11 | D09081P | | 9 | | D09102P | | 9 | | 150, 152-199 |
| 903R | 18 | PA | | | 10-0 | 23-19-11 | D09081P | | 1 | | D09102P | | 1 | | 150, 152-199 |
| YAA | | | | | 0-0 | 23-19-11 | D09081P | =CC | D | | D09102P | =CC | D | | 150, 152-199 |
| W9077 | 286T9077 | | | AIR TO GROUND PUBLIC TELEPHONE - E90-90 SHELF | | | | | | | | | | | |
| 900B | 26 | BW | A | | 5-0 | 23-19-11 | D09065J | | F | | D09082A | | 1B | | 150, 152-199 |
| 900R | 26 | BW | A | | 0-0 | 23-19-11 | D09065J | | E | | D09082A | | 1A | | 150, 152-199 |
| 900Z | | | A | | 0-0 | 23-19-11 | D09065J | | | FA | D09082A | | | FB | 150, 152-199 |
| 901G | 26 | BW | B | | 0-0 | 23-19-11 | D09065J | | C | | D09082A | | 1D | | 150, 152-199 |
| 901Y | 26 | BW | B | | 5-0 | 23-19-11 | D09065J | | B | | D09082A | | 1C | | 150, 152-199 |
| 901Z | | | B | | 0-0 | 23-19-11 | D09065J | | | FA | D09082A | | | FB | 150, 152-199 |
| 902B | 26 | BW | C | | 0-0 | 23-19-11 | D09093J | | F | | D09082A | | 2B | | 150, 152-199 |

WIRE LIST
D280T132

91-21-11
Section W9070
Page 2
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9077 | 286T9077 | | | AIR TO GRONUD PUBLIC TELEPHONE - E90-90 SHELF (continued) | | | | | | | | | | | |
| 902R | 26 | BW | C | 5-0 | 23-19-11 | D09093J | | E | | | D09082A | 2A | | | 150, 152-199 |
| 902Z | | | C | 0-0 | 23-19-11 | D09093J | | | | FC | D09082A | | | FD | 150, 152-199 |
| 903G | 26 | BW | D | 0-0 | 23-19-11 | D09093J | | C | | | D09082A | 2D | | | 150, 152-199 |
| 903Y | 26 | BW | D | 5-0 | 23-19-11 | D09093J | | B | | | D09082A | 2C | | | 150, 152-199 |
| 903Z | | | D | 0-0 | 23-19-11 | D09093J | | | | FC | D09082A | | | FD | 150, 152-199 |
| 904B | 26 | BW | E | 0-0 | 23-19-11 | D09094J | | F | | | D09082A | 3B | | | 150, 152-199 |
| 904R | 26 | BW | E | 5-0 | 23-19-11 | D09094J | | E | | | D09082A | 3A | | | 150, 152-199 |
| 904Z | | | E | 0-0 | 23-19-11 | D09094J | | | | FE | D09082A | | | FF | 150, 152-199 |
| 905G | 26 | BW | F | 0-0 | 23-19-11 | D09094J | | C | | | D09082A | 3D | | | 150, 152-199 |
| 905Y | 26 | BW | F | 5-0 | 23-19-11 | D09094J | | B | | | D09082A | 3C | | | 150, 152-199 |
| 905Z | | | F | 0-0 | 23-19-11 | D09094J | | | | FE | D09082A | | | FF | 150, 152-199 |
| 906B | 24 | PW | G | 0-0 | 23-19-11 | D09095J | | B | | | D09082A | 12B | | | 150, 152-199 |
| 906W | 24 | PW | G | 5-0 | 23-19-11 | D09095J | | A | | | D09082A | 12A | | | 150, 152-199 |
| 906Z | | | G | 0-0 | 23-19-11 | D09095J | | | | FG | D09082A | | | FH | 150, 152-199 |
| 907 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | A | | | D09082A | 6A | | | 150, 152-199 |
| 907B | 24 | PW | H | 0-0 | 23-19-11 | D09095J | | D | | | D09082A | 12D | | | 150, 152-199 |
| 907W | 24 | PW | H | 5-0 | 23-19-11 | D09095J | | C | | | D09082A | 12C | | | 150, 152-199 |
| 907Z | | | H | 0-0 | 23-19-11 | D09095J | | | | FG | D09082A | | | FH | 150, 152-199 |
| 908 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | B | | | D09082A | 6B | | | 150, 152-199 |
| 908B | 24 | PW | I | 0-0 | 23-19-11 | D09095J | | H | | | D09082A | 12F | | | 150, 152-199 |
| 908W | 24 | PW | I | 5-0 | 23-19-11 | D09095J | | G | | | D09082A | 12E | | | 150, 152-199 |
| 908Z | | | I | 0-0 | 23-19-11 | D09095J | | | | FI | D09082A | | | FJ | 150, 152-199 |
| 909 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | C | | | D09082A | 6C | | | 150, 152-199 |
| 909B | 24 | PW | J | 0-0 | 23-19-11 | D09095J | | F | | | D09082A | 12H | | | 150, 152-199 |
| 909W | 24 | PW | J | 5-0 | 23-19-11 | D09095J | | E | | | D09082A | 12G | | | 150, 152-199 |
| 909Z | | | J | 0-0 | 23-19-11 | D09095J | | | | FI | D09082A | | | FJ | 150, 152-199 |
| 910 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | D | | | D09082A | 6D | | | 150, 152-199 |
| 911 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | E | | | D09082A | 6E | | | 150, 152-199 |
| 912 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | F | | | D09082A | 6F | | | 150, 152-199 |
| 913 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | G | | | D09082A | 6G | | | 150, 152-199 |
| 914 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | H | | | D09082A | 6H | | | 150, 152-199 |
| 915 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | J | | | D09082A | 6J | | | 150, 152-199 |
| 916 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | K | | | D09082A | 6K | | | 150, 152-199 |
| 917 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | L | | | D09082A | 7A | | | 150, 152-199 |
| 918 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | M | | | D09082A | 7B | | | 150, 152-199 |
| 919 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | N | | | D09082A | 7C | | | 150, 152-199 |
| 920 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | P | | | D09082A | 7D | | | 150, 152-199 |
| 921 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | R | | | D09082A | 7E | | | 150, 152-199 |
| 922 | 24 | PK | | 5-0 | 23-19-11 | D09096J | | S | | | D09082A | 7F | | | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W9070

Page 3

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9077 | 286T9077 | | | AIR TO GRONUD PUBLIC TELEPHONE - E90-90 SHELF (continued) | | | | | | | | | | | |
| 923 | 24 | | PK | | 5-0 | 23-19-11 | D09096J | | T | | D09082A | | 7G | | 150, 152-199 |
| 924 | 24 | | PK | | 5-0 | 23-19-11 | D09096J | | U | | D09082A | | 7H | | 150, 152-199 |
| 925 | 24 | | PK | | 5-0 | 23-19-11 | D09096J | | V | | D09082A | | 7J | | 150, 152-199 |
| 926 | 24 | | PK | | 5-0 | 23-19-11 | D09096J | | W | | D09082A | | 7K | | 150, 152-199 |
| 927 | 24 | | PK | | 5-0 | 23-19-11 | D09096J | | X | | D09082A | | 8A | | 150, 152-199 |
| 928 | 24 | | PK | | 5-0 | 23-19-11 | D09096J | | Y | | D09082A | | 8B | | 150, 152-199 |
| 929 | 24 | | PK | | 5-0 | 23-19-11 | D09096J | | Z | | D09082A | | 8C | | 150, 152-199 |
| 930 | 24 | | PK | | 5-0 | 23-19-11 | D09096J | | A- | | D09082A | | 8D | | 150, 152-199 |
| 931 | 24 | | PK | | 5-0 | 23-19-11 | D09096J | | B- | | D09082A | | 8E | | 150, 152-199 |
| 932B | 24 | | PW | L | 0-0 | 23-19-11 | D09063J | | B | | D09082A | | 4G | | 150, 152-199 |
| 932W | 24 | | PW | L | 5-0 | 23-19-11 | D09063J | | A | | D09082A | | 4F | | 150, 152-199 |
| 932Z | | | | L | 0-0 | 23-19-11 | D09063J | | | FL | D09082A | | | FM | 150, 152-199 |
| 933B | 24 | | PW | M | 0-0 | 23-19-11 | D09063J | | E | | D09082A | | 4J | | 150, 152-199 |
| 933W | 24 | | PW | M | 5-0 | 23-19-11 | D09063J | | D | | D09082A | | 4H | | 150, 152-199 |
| 933Z | | | | M | 0-0 | 23-19-11 | D09063J | | | FL | D09082A | | | FM | 150, 152-199 |
| 934 | 24 | | PK | | 5-0 | 23-19-11 | D09063J | | F | | D09082A | | 8J | | 150, 152-199 |
| 935 | 24 | | PK | | 5-0 | 23-19-11 | D09063J | | G | | D09082A | | 8K | | 150, 152-199 |
| 936B | 24 | | PW | N | 0-0 | 23-19-11 | D09063J | | A- | | D09082A | | 5B | | 150, 152-199 |
| 936W | 24 | | PW | N | 5-0 | 23-19-11 | D09063J | | Z | | D09082A | | 5A | | 150, 152-199 |
| 936Z | | | | N | 0-0 | 23-19-11 | D09063J | | | FN | D09082A | | | FO | 150, 152-199 |
| 937B | 24 | | PW | O | 0-0 | 23-19-11 | D09063J | | D- | | D09082A | | 5D | | 150, 152-199 |
| 937W | 24 | | PW | O | 5-0 | 23-19-11 | D09063J | | C- | | D09082A | | 5C | | 150, 152-199 |
| 937Z | | | | O | 0-0 | 23-19-11 | D09063J | | | FN | D09082A | | | FO | 150, 152-199 |
| 938B | 24 | | PW | P | 0-0 | 23-19-11 | D09063J | | F- | | D09082A | | 8G | | 150, 152-199 |
| 938W | 24 | | PW | P | 5-0 | 23-19-11 | D09063J | | E- | | D09082A | | 8F | | 150, 152-199 |
| 938Z | | | | P | 0-0 | 23-19-11 | D09063J | | G- | | D09082A | | 8H | | 150, 152-199 |
| 939 | 24 | | PK | | 5-0 | 23-19-11 | D09063J | | H- | | D09082A | | 14A | | 150, 152-199 |
| 940 | 24 | | PK | | 5-0 | 23-19-11 | D09063J | | H | | D09082A | | 9C | | 150, 152-199 |
| 941 | 24 | | PK | | 5-0 | 23-19-11 | D09063J | | J | | D09082A | | 9D | | 150, 152-199 |
| 942 | 24 | | PK | | 5-0 | 23-19-11 | D09063J | | J- | | D09082A | | 9B | | 150, 152-199 |
| 943 | 24 | | PK | | 5-0 | 23-19-11 | D09063J | | I- | | D09082A | | 9A | | 150, 152-199 |
| 944 | 24 | | PK | | 5-0 | 23-19-11 | D09063J | | K | | D09082A | | 9E | | 150, 152-199 |
| 945 | 24 | | PK | | 5-0 | 23-19-11 | D09063J | | L | | D09082A | | 9F | | 150, 152-199 |
| 946B | 24 | | PW | Q | 0-0 | 23-19-11 | D09063J | | N | | D09082A | | 9H | | 150, 152-199 |
| 946W | 24 | | PW | Q | 5-0 | 23-19-11 | D09063J | | M | | D09082A | | 9G | | 150, 152-199 |
| 946Z | | | | Q | 0-0 | 23-19-11 | D09063J | | P | | D09082A | | 9J | | 150, 152-199 |
| 947 | 24 | | PK | | 5-0 | 23-19-11 | D09063J | | R | | D09082A | | 10A | | 150, 152-199 |
| 948 | 24 | | PK | | 5-0 | 23-19-11 | D09063J | | S | | D09082A | | 10B | | 150, 152-199 |
| 949 | 24 | | PK | | 5-0 | 23-19-11 | D09063J | | T | | D09082A | | 10C | | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W9070

Page 4

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|--------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W9077 | 286T9077 | | | AIR TO GRONUD PUBLIC TELEPHONE - E90-90 SHELF (continued) | | | | | | | | | | | | |
| 950 | 24 | | PK | 5-0 | 23-19-11 | D09063J | | U | | | | D09082A | 10D | | | 150, 152-199 |
| 951 | 24 | | PK | 5-0 | 23-19-11 | D09063J | | V | | | | D09082A | 10E | | | 150, 152-199 |
| 952 | 24 | | PK | 5-0 | 23-19-11 | D09063J | | W | | | | D09082A | 10F | | | 150, 152-199 |
| 953 | 24 | | PK | 5-0 | 23-19-11 | D09063J | | X | | | | D09082A | 10G | | | 150, 152-199 |
| 954 | 24 | | PK | 5-0 | 23-19-11 | D09063J | | Y | | | | D09082A | 10H | | | 150, 152-199 |
| 955 | 24 | | PK | 5-0 | 23-19-11 | D09063J | | N- | | | | D09082B | 9A | | | 150, 152-199 |
| 956 | 24 | | PK | 5-0 | 23-19-11 | D09063J | | P- | | | | D09082B | 9B | | | 150, 152-199 |
| 957 | 24 | | PK | 5-0 | 23-19-11 | D09063J | | Q- | | | | D09082B | 9C | | | 150, 152-199 |
| 958 | 24 | | PK | 5-0 | 23-19-11 | D09063J | | R- | | | | D09082B | 9D | | | 150, 152-199 |
| 959 | 24 | | PK | 5-0 | 23-19-11 | D09063J | | K- | | | | D09082B | 13C | | | 150, 152-199 |
| 960 | 24 | | PK | 5-0 | 23-19-11 | D09063J | | M- | | | | D09082B | 13D | | | 150, 152-199 |
| 961B | 24 | | PW | R | 0-0 | 23-19-11 | D09066J | | F | | | D09082B | 1B | | | 150, 152-199 |
| 961R | 24 | | PW | R | 5-0 | 23-19-11 | D09066J | | E | | | D09082B | 1A | | | 150, 152-199 |
| 961Z | | | | | 0-0 | 23-19-11 | D09066J | | | | FP | D09082B | | | FQ | 150, 152-199 |
| 962G | 24 | | PW | S | 0-0 | 23-19-11 | D09066J | | D | | | D09082B | 1D | | | 150, 152-199 |
| 962Y | 24 | | PW | S | 5-0 | 23-19-11 | D09066J | | C | | | D09082B | 1C | | | 150, 152-199 |
| 962Z | | | | S | 0-0 | 23-19-11 | D09066J | | | | FP | D09082B | | | FQ | 150, 152-199 |
| 963 | 22 | | PA | | 3-0 | 23-19-11 | D09066J | | | | FZ | E090-90 | = G | E | | 150, 152-199 |
| 964GY | 24 | | PW | T | 5-0 | 23-19-11 | D09066J | | A | | | D09097J | B | | | 150, 152-199 |
| 964W | 24 | | PW | T | 0-0 | 23-19-11 | D09066J | | B | | | D09097J | C | | | 150, 152-199 |
| 964Z | | | | T | 0-0 | 23-19-11 | D09066J | | | | FZ | D09097J | P | | | 150, 152-199 |
| 965B | 24 | | PW | U | 0-0 | 23-19-11 | D09098J | | F | | | D09082B | 10B | | | 150, 152-199 |
| 965R | 24 | | PW | U | 5-0 | 23-19-11 | D09098J | | E | | | D09082B | 10A | | | 150, 152-199 |
| 965Z | | | | U | 0-0 | 23-19-11 | D09098J | | | | FR | D09082B | | | FS | 150, 152-199 |
| 966G | 24 | | PW | V | 0-0 | 23-19-11 | D09098J | | D | | | D09082B | 10D | | | 150, 152-199 |
| 966Y | 24 | | PW | V | 5-0 | 23-19-11 | D09098J | | C | | | D09082B | 10C | | | 150, 152-199 |
| 966Z | | | | V | 0-0 | 23-19-11 | D09098J | | | | FR | D09082B | | | FS | 150, 152-199 |
| 967 | 22 | | PA | | 3-0 | 23-19-11 | D09098J | | | | FK | E090-90 | = G | E | | 150, 152-199 |
| 968GY | 24 | | PW | W | 5-0 | 23-19-11 | D09098J | | A | | | D09097J | A | | | 150, 152-199 |
| 968W | 24 | | PW | W | 0-0 | 23-19-11 | D09098J | | B | | | D09097J | M | | | 150, 152-199 |
| 968Z | | | | W | 0-0 | 23-19-11 | D09098J | | | | FK | D09097J | N | | | 150, 152-199 |
| 969B | 24 | | PW | X | 0-0 | 23-19-11 | D09067J | | F | | | D09082B | 10J | | | 150, 152-199 |
| 969R | 24 | | PW | X | 5-0 | 23-19-11 | D09067J | | E | | | D09082B | 10K | | | 150, 152-199 |
| 969Z | | | | X | 0-0 | 23-19-11 | D09067J | | | | FT | D09082B | | | FU | 150, 152-199 |
| 970G | 24 | | PW | Y | 0-0 | 23-19-11 | D09067J | | D | | | D09082B | 10G | | | 150, 152-199 |
| 970Y | 24 | | PW | Y | 5-0 | 23-19-11 | D09067J | | C | | | D09082B | 10H | | | 150, 152-199 |
| 970Z | | | | Y | 0-0 | 23-19-11 | D09067J | | | | FT | D09082B | | | FU | 150, 152-199 |
| 971 | 22 | | PA | | 3-0 | 23-19-11 | D09067J | | | | F2 | E090-90 | = G | E | | 150, 152-199 |
| 972GY | 24 | | PW | Z | 5-0 | 23-19-11 | D09067J | | A | | | D09097J | E | | | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W9070

Page 5

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9077 | 286T9077 | | | AIR TO GRONUD PUBLIC TELEPHONE - E90-90 SHELF (continued) | | | | | | | | | | | |
| 972W | 24 | PW | Z | | 0-0 | 23-19-11 | D09067J | | B | | D09097J | | F | | 150, 152-199 |
| 972Z | | | Z | | 0-0 | 23-19-11 | D09067J | | | F2 | D09097J | | S | | 150, 152-199 |
| 973B | 24 | PW | AA | | 0-0 | 23-19-11 | D09099J | | F | | D09082B | | 11B | | 150, 152-199 |
| 973R | 24 | PW | AA | | 5-0 | 23-19-11 | D09099J | | E | | D09082B | | 11A | | 150, 152-199 |
| 973Z | | | AA | | 0-0 | 23-19-11 | D09099J | | | FV | D09082B | | | FW | 150, 152-199 |
| 974G | 24 | PW | AB | | 0-0 | 23-19-11 | D09099J | | D | | D09082B | | 11D | | 150, 152-199 |
| 974Y | 24 | PW | AB | | 5-0 | 23-19-11 | D09099J | | C | | D09082B | | 11C | | 150, 152-199 |
| 974Z | | | AB | | 0-0 | 23-19-11 | D09099J | | | FV | D09082B | | | FW | 150, 152-199 |
| 975 | 22 | PA | | | 3-0 | 23-19-11 | D09099J | | | F3 | E090-90 | =G | E | | 150, 152-199 |
| 976GY | 24 | PW | AC | | 5-0 | 23-19-11 | D09099J | | A | | D09097J | | H | | 150, 152-199 |
| 976W | 24 | PW | AC | | 0-0 | 23-19-11 | D09099J | | B | | D09097J | | J | | 150, 152-199 |
| 976Z | | | AC | | 0-0 | 23-19-11 | D09099J | | | F3 | D09097J | | T | | 150, 152-199 |
| 977B | 24 | PW | AD | | 0-0 | 23-19-11 | D09100J | | F | | D09082B | | 11J | | 150, 152-199 |
| 977R | 24 | PW | AD | | 5-0 | 23-19-11 | D09100J | | E | | D09082B | | 11K | | 150, 152-199 |
| 977Z | | | AD | | 0-0 | 23-19-11 | D09100J | | | FX | D09082B | | | FY | 150, 152-199 |
| 978G | 24 | PW | AE | | 0-0 | 23-19-11 | D09100J | | D | | D09082B | | 11G | | 150, 152-199 |
| 978Y | 24 | PW | AE | | 5-0 | 23-19-11 | D09100J | | C | | D09082B | | 11H | | 150, 152-199 |
| 978Z | | | AE | | 0-0 | 23-19-11 | D09100J | | | FX | D09082B | | | FY | 150, 152-199 |
| 979 | 22 | PA | | | 3-0 | 23-19-11 | D09100J | | | F4 | E090-90 | =G | E | | 150, 152-199 |
| 980GY | 24 | PW | AF | | 5-0 | 23-19-11 | D09100J | | A | | D09097J | | K | | 150, 152-199 |
| 980W | 24 | PW | AF | | 0-0 | 23-19-11 | D09100J | | B | | D09097J | | L | | 150, 152-199 |
| 980Z | | | AF | | 0-0 | 23-19-11 | D09100J | | | F4 | D09097J | | U | | 150, 152-199 |
| 981 | 20 | PA | | | 5-0 | 23-19-11 | D09061P | | 2 | | B09009 | LUG | E | | 150, 152-199 |
| 982 | 16 | PA | | | 5-0 | 23-19-11 | D09082C | | 3 | | D09060J | | D- | | 150, 152-199 |
| 983 | 20 | PA | | | 5-0 | 23-19-11 | D09061P | | 1 | | B09009 | LUG | E | | 150, 152-199 |
| 984 | 16 | PA | | | 5-0 | 23-19-11 | D09082C | | 2 | | D09060J | | C- | | 150, 152-199 |
| 985B | 16 | Q5 | NA | | 0-0 | 23-19-11 | D09098J | | M | | D09060J | | Z | | 150, 152-199 |
| 985G | 16 | Q5 | NA | | 0-0 | 23-19-11 | D09098J | | J | | D09060J | | Y | | 150, 152-199 |
| 985O | 16 | Q5 | NA | | 0-0 | 23-19-11 | D09098J | | L | | D09060J | | X | | 150, 152-199 |
| 985W | 16 | Q5 | NA | | 5-0 | 23-19-11 | D09098J | | K | | D09060J | | A- | | 150, 152-199 |
| 985Z | | | NA | | 0-0 | 23-19-11 | D09098J | | | FK | D09060J | | B- | | 150, 152-199 |
| 986B | 16 | Q5 | NB | | 0-0 | 23-19-11 | D09066J | | M | | D09060J | | U | | 150, 152-199 |
| 986G | 16 | Q5 | NB | | 0-0 | 23-19-11 | D09066J | | J | | D09060J | | T | | 150, 152-199 |
| 986O | 16 | Q5 | NB | | 0-0 | 23-19-11 | D09066J | | L | | D09060J | | S | | 150, 152-199 |
| 986W | 16 | Q5 | NB | | 5-0 | 23-19-11 | D09066J | | K | | D09060J | | V | | 150, 152-199 |
| 986Z | | | NB | | 0-0 | 23-19-11 | D09066J | | | FZ | D09060J | | W | | 150, 152-199 |
| 987B | 16 | Q5 | NC | | 0-0 | 23-19-11 | D09067J | | M | | D09060J | | N | | 150, 152-199 |
| 987G | 16 | Q5 | NC | | 0-0 | 23-19-11 | D09067J | | J | | D09060J | | M | | 150, 152-199 |
| 987O | 16 | Q5 | NC | | 0-0 | 23-19-11 | D09067J | | L | | D09060J | | L | | 150, 152-199 |

WIRE LIST
D280T132

91-21-11
Section W9070
Page 6
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-----------------|----|----|--|-------------|---------|-------|------|------|--------|-------|------|---------|--------|---|-------------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W9077 | 286T9077 | | | AIR TO GRONUD PUBLIC TELEPHONE - E90-90 SHELF (continued) | | | | | | | | | | | | | |
| 987W | 16 | Q5 | NC | 5-0 | 23-19-11 | D09067J | | K | | | | | D09060J | P | | | 150, 152-199 |
| 987Z | | | NC | 0-0 | 23-19-11 | D09067J | | | | | | | D09060J | R | | | 150, 152-199 |
| 988B | 16 | Q5 | ND | 0-0 | 23-19-11 | D09099J | | M | | | | | D09060J | H | | | 150, 152-199 |
| 988G | 16 | Q5 | ND | 0-0 | 23-19-11 | D09099J | | J | | | | | D09060J | G | | | 150, 152-199 |
| 988O | 16 | Q5 | ND | 0-0 | 23-19-11 | D09099J | | L | | | | | D09060J | F | | | 150, 152-199 |
| 988W | 16 | Q5 | ND | 5-0 | 23-19-11 | D09099J | | K | | | | | D09060J | J | | | 150, 152-199 |
| 988Z | | | ND | 0-0 | 23-19-11 | D09099J | | | | | | | D09060J | K | | | 150, 152-199 |
| 989B | 16 | Q5 | NE | 0-0 | 23-19-11 | D09100J | | M | | | | | D09060J | B | | | 150, 152-199 |
| 989G | 16 | Q5 | NE | 0-0 | 23-19-11 | D09100J | | J | | | | | D09060J | C | | | 150, 152-199 |
| 989O | 16 | Q5 | NE | 0-0 | 23-19-11 | D09100J | | L | | | | | D09060J | A | | | 150, 152-199 |
| 989W | 16 | Q5 | NE | 5-0 | 23-19-11 | D09100J | | K | | | | | D09060J | D | | | 150, 152-199 |
| 989Z | | | NE | 0-0 | 23-19-11 | D09100J | | | | | | | D09060J | E | | | 150, 152-199 |
| 990 | 16 | PA | | 5-0 | 23-19-11 | D09082C | | 8 | | | | | E090-90 | =G | E | | 150, 152-199 |
| FR2 | | | | 0-0 | 23-19-11 | D09067J | | G | | | | | D09067J | | | F2 | 150, 152-199 |
| FR3 | | | | 0-0 | 23-19-11 | D09099J | | G | | | | | D09099J | | | F3 | 150, 152-199 |
| FR4 | | | | 0-0 | 23-19-11 | D09100J | | G | | | | | D09100J | | | F4 | 150, 152-199 |
| FRA | | | | 0-0 | 23-19-11 | D09065J | | D | | | | | D09065J | | | FA | 150, 152-199 |
| FRB | | | | 0-0 | 23-19-11 | D09082A | | 1E | | | | | D09082A | | | FB | 150, 152-199 |
| FRC | | | | 0-0 | 23-19-11 | D09093J | | D | | | | | D09093J | | | FC | 150, 152-199 |
| FRD | | | | 0-0 | 23-19-11 | D09082A | | 2E | | | | | D09082A | | | FD | 150, 152-199 |
| FRE | | | | 0-0 | 23-19-11 | D09094J | | D | | | | | D09094J | | | FE | 150, 152-199 |
| FRF | | | | 0-0 | 23-19-11 | D09082A | | 3E | | | | | D09082A | | | FF | 150, 152-199 |
| FRG | | | | 0-0 | 23-19-11 | D09095J | | J | | | | | D09095J | | | FG | 150, 152-199 |
| FRH | | | | 0-0 | 23-19-11 | D09082A | | 12J | | | | | D09082A | | | FH | 150, 152-199 |
| FRI | | | | 0-0 | 23-19-11 | D09095J | | K | | | | | D09095J | | | FI | 150, 152-199 |
| FRJ | | | | 0-0 | 23-19-11 | D09082A | | 12K | | | | | D09082A | | | FJ | 150, 152-199 |
| FRK | | | | 0-0 | 23-19-11 | D09098J | | G | | | | | D09098J | | | FK | 150, 152-199 |
| FRL | | | | 0-0 | 23-19-11 | D09063J | | C | | | | | D09063J | | | FL | 150, 152-199 |
| FRM | | | | 0-0 | 23-19-11 | D09082A | | 4K | | | | | D09082A | | | FM | 150, 152-199 |
| FRN | | | | 0-0 | 23-19-11 | D09063J | | B- | | | | | D09063J | | | FN | 150, 152-199 |
| FRO | | | | 0-0 | 23-19-11 | D09082A | | 5E | | | | | D09082A | | | FO | 150, 152-199 |
| FRP | | | | 0-0 | 23-19-11 | D09066J | | H | | | | | D09066J | | | FP | 150, 152-199 |
| FRQ | | | | 0-0 | 23-19-11 | D09082B | | 1E | | | | | D09082B | | | FQ | 150, 152-199 |
| FRR | | | | 0-0 | 23-19-11 | D09098J | | H | | | | | D09098J | | | FR | 150, 152-199 |
| FRS | | | | 0-0 | 23-19-11 | D09082B | | 10E | | | | | D09082B | | | FS | 150, 152-199 |
| FRT | | | | 0-0 | 23-19-11 | D09067J | | H | | | | | D09067J | | | FT | 150, 152-199 |
| FRU | | | | 0-0 | 23-19-11 | D09082B | | 10F | | | | | D09082B | | | FU | 150, 152-199 |
| FRV | | | | 0-0 | 23-19-11 | D09099J | | H | | | | | D09099J | | | FV | 150, 152-199 |
| FRW | | | | 0-0 | 23-19-11 | D09082B | | 11E | | | | | D09082B | | | FW | 150, 152-199 |

WIRE LIST

D280T132

91-21-11

Section W9070

Page 7

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|--|-------|----------|-------------|------|------|-----------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9077 | 286T9077 | | | AIR TO GRONUD PUBLIC TELEPHONE - E90-90 SHELF (continued) | | | | | | | | | | | |
| FRX | | | | | 0-0 | 23-19-11 | D09100J | | H | | D09100J | | | FX | 150, 152-199 |
| FRY | | | | | 0-0 | 23-19-11 | D09082B | | 11F | | D09082B | | | FY | 150, 152-199 |
| FRZ | | | | | 0-0 | 23-19-11 | D09066J | | G | | D09066J | | | FZ | 150, 152-199 |

WIRE LIST
D280T132

91-21-11
Section W9070
Page 8 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | |
|------------------------|-----------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W9080 | 286T9080 | | | AIR GROUND TO PUBLIC TELEPHONE - E090-90 SHELF | | | | | | | | | | |
| 901 | 10 | PA | | 3-0 | 23-19-11 | GD09004 | S.. | E | | GD09003 | S.. | E | | 150, 152-199 |
| W9081 | 286T9081 | | | AIR TO GROUND PUBLIC TELEPHONE - CONTROL POWER | | | | | | | | | | |
| 901 | 20 | PA | | 24-0 | 23-19-11 | D05848P | | 1 | | D04906P | | 5 | | 150, 152-199 |

WIRE LIST
D280T132

91-21-11
Section W9080
Page 1 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|-------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9090 | 286T9090 | | | F/O INSTRUMENT PANEL | | | | | | | | | | | |
| 901 | 22 | | PA | | 50-0 | 34-46-13 | D09131 | | | | 18 | | | | 150, 152-199, 275-299 |
| 901W | 24 | | PW | B | 7-0 | 34-46-13 | D04889J | | | | 5 | | | | 150, 152-199, 275-299 |
| 901WB | 24 | | PW | B | 0-0 | 34-46-13 | D04889J | | | | 6 | | | | 150, 152-199, 275-299 |
| 901Z | | | | B | 0-0 | 34-46-13 | D04889J | | | | 7 | | | | 150, 152-199, 275-299 |
| 902 | 22 | | PA | | 50-0 | 34-46-13 | D09131 | | | | 12 | | | | 150, 152-199, 275-299 |
| 902W | 24 | | PW | A | 7-0 | 34-46-13 | D04889J | | | | 20 | | | | 150, 152-199, 275-299 |
| 902WB | 24 | | PW | A | 0-0 | 34-46-13 | D04889J | | | | 21 | | | | 150, 152-199, 275-299 |
| 902Z | | | | A | 0-0 | 34-46-13 | D04889J | | | | 22 | | | | 150, 152-199, 275-299 |
| 903 | 22 | | PA | | 50-0 | 34-46-13 | D09131 | | | | 16 | | | | 150, 152-199, 275-299 |
| 903W | 24 | | PW | D | 7-0 | 34-46-13 | D05365J | | | | 1 | | | | 150, 152-199, 275-299 |
| 903WB | 24 | | PW | D | 0-0 | 34-46-13 | D05365J | | | | 2 | | | | 150, 152-199, 275-299 |
| 903Z | | | | D | 0-0 | 34-46-13 | D05365J | | | | 3 | | | | 150, 152-199, 275-299 |
| 904 | 22 | | PA | | 50-0 | 34-46-13 | D09131 | | | | 14 | | | | 150, 152-199, 275-299 |
| 904W | 24 | | PW | C | 7-0 | 34-46-13 | D05365J | | | | 14 | | | | 150, 152-199, 275-299 |
| 904WB | 24 | | PW | C | 0-0 | 34-46-13 | D05365J | | | | 15 | | | | 150, 152-199, 275-299 |
| 904Z | | | | C | 0-0 | 34-46-13 | D05365J | | | | 10 | | | | 150, 152-199, 275-299 |
| 905 | 22 | | PA | | 30-0 | 34-46-13 | SP09003 | | | | | 9 | | | 150, 152-199, 275-299 |
| 906 | 22 | | PA | | 30-0 | 34-46-13 | SP00341 | | | | | 9 | | | 150, 152-199, 275-299 |
| 907 | 22 | | PA | | 30-0 | 34-46-13 | SP09005 | | | | | W | | | 150, 152-199, 275-299 |
| 908 | 22 | | PA | | 50-0 | 34-46-13 | D09124 | | | | 8 | | | | 150, 152-199, 275-299 |
| 909 | 22 | | PA | | 50-0 | 34-46-13 | D09124 | | | | 11 | | | | 150, 152-199, 275-299 |
| 910 | 22 | | PA | | 50-0 | 34-46-13 | D09124 | | | | 2 | | | | 150, 152-199, 275-299 |
| 911 | 22 | | PA | | 50-0 | 34-46-13 | D09124 | | | | 9 | | | | 150, 152-199, 275-299 |
| 912 | 22 | | PA | | 50-0 | 34-46-13 | D09124 | | | | 6 | | | | 150, 152-199, 275-299 |
| 913 | 22 | | PA | | 50-0 | 34-46-13 | D09124 | | | | 4 | | | | 150, 152-199, 275-299 |
| 914 | 22 | | PA | | 30-0 | 34-46-13 | SP09004 | | | | | 9 | | | 150, 152-199, 275-299 |
| 915 | 20 | | PA | | 5-0 | 34-46-13 | D09131 | | | | 11 | | | | 150, 152-199, 275-299 |
| 916 | 22 | | PA | | 12-0 | 33-16-13 | D09131 | | | | 13 | | | | 150, 152-199, 275-299 |
| 917 | 22 | | PA | | 12-0 | 33-16-13 | D09131 | | | | 15 | | | | 150, 152-199, 275-299 |
| 918 | 20 | | PA | | 5-0 | 34-46-13 | D09131 | | | | 17 | | | | 150, 152-199, 275-299 |
| 919 | 20 | | PA | | 8-0 | 34-46-13 | D09124 | | | | 1 | | | | 150, 152-199, 275-299 |
| 920 | 22 | | PA | | 12-0 | 33-16-13 | D09124 | | | | 3 | | | | 150, 152-199, 275-299 |
| 921 | 22 | | PA | | 12-0 | 33-16-13 | D09124 | | | | 5 | | | | 150, 152-199, 275-299 |
| 922 | 20 | | PA | | 8-0 | 34-46-13 | D09124 | | | | 7 | | | | 150, 152-199, 275-299 |
| 923 | 20 | | PA | | 8-0 | 34-46-13 | D09124 | | | | 10 | | | * | 150, 152-199, 275-299 |
| 924 | 20 | | PA | | 8-0 | 34-46-13 | D09124 | | | | 12 | | | | 150, 152-199, 275-299 |
| 925 | 20 | | PA | | 8-0 | 33-13-13 | GD03104 | | | | A.. | 2 | | | 150, 152-199, 275-299 |
| 926 | 20 | | PA | | 8-0 | 33-13-13 | SPZ0001 | | | | | S | | | 150, 152-199, 275-299 |
| 927 | 22 | | PA | | 28-0 | 34-46-12 | D09123J | | | | 27 | | | | 150, 152-199, 275-299 |

WIRE LIST
D280T132



| Bundle No. | Part Number | | | Description | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|--------|-------|---------|------|--------|-----------------------|
| | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | |
| W9091 | 286T9091 | | | GROUND PROXIMITY WARNING SYSTEM | | | | | | | | | |
| 01CO | | | | MA | 0-0 | 34-46-11 | D09125P | = C1 | | D00435C | = C1 | | 150, 152-199, 275-299 |
| 01CX | | | 0F | MA | 5-0 | 34-46-11 | D09125P | = A1 | | D00435C | = 1 | | 150, 152-199, 275-299 |
| W9092 | 286T9092 | | | GROUND PROXIMITY WARNING SYSTEM | | | | | | | | | |
| 01CO | | | | MA | 0-0 | 34-46-11 | D09126 | = C1 | | D09125J | = C1 | | 150, 152-199, 275-299 |
| 01CX | | | 0F | MA | 60-0 | 34-46-11 | D09126 | = A1 | | D09125J | = A1 | | 150, 152-199, 275-299 |



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|-------------------|--------------------|----|----|--------------------|--|----------|-------------|--------|------|-----------|---------|---------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9119 | 286T9119 | | | | COAX-SATCOM,M1787 HIGH PWR RLY TO E10 SHELF | | | | | | | | | | |
| 01CO | | | | A | 0-0 | 23-25-17 | D02671 | = | C1 | | D06183P | = | C1 | | 150, 153-199 |
| 01CX | | | | JB | A | 18-0 | 23-25-17 | D02671 | = | A1 | | D06183P | = | A1 | 150, 153-199 |

WIRE LIST
D280T132

91-21-11
Section W9110
Page 1 End
Mar 09/2006

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|------|-------------|---------|--|------|------|---------|-------|------|------|--------|-----------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W9120 | 286T9120 | | | | | | COAX-SATCOM,M1782 HPA TO AP1001 (SPLITTER) | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-12 | D02651A | = | C71 | | D06187J | = | C1 | | | 150, 153-155, 162-165 | |
| 01CX | | 78 | A | 1-2 | 23-25-12 | D02651A | = | 71 | | D06187J | = | A1 | | | 150, 153-155, 162-165 | |
| W9121 | 286T9121 | | | | | | COAX-SATCOM,M1786 COMBINER TO E9 SHELF | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-12 | D06177J | = | C1 | | D02665 | = | C1 | | | 150, 153-199 | |
| 01CX | | 78 | A | 48-0 | 23-25-12 | D06177J | = | A1 | | D02665 | = | A1 | | | 150, 153-199 | |
| W9122 | 286T9122 | | | | | | COAX-SATCOM, M1787 HIGHPWR RLY TO M1789, LNA/DIP, L | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-17 | D02707 | = | C1 | | D02673 | = | C1 | | | 150, 153-199 | |
| 01CX | | | JB | 11-6 | 23-25-17 | D02707 | = | A1 | | D02673 | = | A1 | | | 150, 153-199 | |
| W9123 | 286T9123 | | | | | | COAX-SATCOM, E9 TO E10 | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-12 | D06187P | = | C1 | | D06175J | = | C1 | | | 150, 153-199 | |
| 01CX | | 78 | A | 65-0 | 23-25-12 | D06187P | = | A1 | | D06175J | = | A1 | | | 150, 153-199 | |
| W9124 | 286T9124 | | | | | | COAX-SATCOM, M1787 HIGHPWR RLY TO M1789, LNA/DIP, L | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-17 | D02711 | = | C1 | | D02687 | = | C1 | | | 150, 153-199 | |
| 01CX | | | JB | 11-6 | 23-25-17 | D02711 | = | A1 | | D02687 | = | A1 | | | 150, 153-199 | |
| W9125 | 286T9125 | | | | | | COAX-SATCOM,M1790 LNA/DIP,R TO M1787,HIGH PWR RLY | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-17 | D02675 | = | C1 | | D02715 | = | C1 | | | 150, 153-199 | |
| 01CX | | | JB | 12-0 | 23-25-17 | D02675 | = | A1 | | D02715 | = | A1 | | | 150, 153-199 | |
| W9126 | 286T9126 | | | | | | COAX-SATCOM,M1782 HPA TO AP1101 (LNA OR HPR) | | | | | | | | | |
| 01CO | | | C | 0-0 | 23-25-17 | D06183J | = | C1 | | D02651B | = | C71 | | | 150, 153-155, 162-165 | |
| 01CX | | 78 | C | 2-0 | 23-25-17 | D06183J | = | A1 | | D02651B | = | 71 | | | 150, 153-155, 162-165 | |
| W9127 | 286T9127 | | | | | | COAX-SATCOM,M1785 COMBINER TO M1790 LNA/DIP,RIGHT | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-17 | D02667 | = | C1 | | D02713 | = | C1 | | | 150, 153-199 | |
| 01CX | | 78 | A | 12-0 | 23-25-17 | D02667 | = | A1 | | D02713 | = | A1 | | | 150, 153-199 | |
| W9128 | 286T9128 | | | | | | COAX-SATCOM, M1787 HIGHPWR RLY TO M1789, LNA/DIP, L | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-17 | D02703 | = | C1 | | D02691 | = | C1 | | | 150, 153-199 | |
| 01CX | | | JB | 11-6 | 23-25-17 | D02703 | = | A1 | | D02691 | = | A1 | | | 150, 153-199 | |
| W9129 | 286T9129 | | | | | | COAX-SATCOM,M1785 COMBINER TO M1789 LNA/DIP,LEFT | | | | | | | | | |
| 01CO | | | A | 0-0 | 23-25-17 | D02705 | = | C1 | | D02669 | = | C1 | | | 150, 153-199 | |

WIRE LIST

D280T132

91-21-11

Section W9120

Page 1

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------------------|-----------------|----|----|-------------|---|----------|--------|------|------|--------|--------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9129 | 286T9129 | | | | COAX-SATCOM,M1785 COMBINER TO M1789 LNA/DIP,LEFT (continued) | | | | | | | | | | |
| 01CX | | 78 | A | | 12-0 | 23-25-17 | D02705 | = | A1 | | D02669 | = | A1 | | 150, 153-199 |

WIRE LIST
D280T132

91-21-11
Section W9120
Page 2 End
Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9158 | 286T9158 | | | PED POWER OUTLETS - P36 LEFT MISC ELEC EQUIP PNL | | | | | | | | | | | |
| 001 | 12 | PA | | | 10-0 | 24-51-13 | C09042 | A01 | D | | C00342 | A02 | D | | 150, 153, 157, 165-199 |
| 002 | 12 | PA | | | 10-0 | 24-51-13 | C09042 | B01 | D | | C00342 | B02 | D | | 150, 153, 157, 165-199 |
| 003 | 12 | PA | | | 10-0 | 24-51-13 | C09042 | C01 | D | | C00342 | C02 | D | | 150, 153, 157, 165-199 |
| 004 | 12 | PA | | | 10-0 | 25-25-23 | D09299J | | 3 | | C09042 | A02 | D | | 150, 153, 157, 165-199 |
| 005 | 12 | PA | | | 10-0 | 25-25-23 | D09299J | | 2 | | C09042 | B02 | D | | 150, 153, 157, 165-199 |
| 006 | 12 | PA | | | 10-0 | 25-25-23 | D09299J | | 1 | | C09042 | C02 | D | | 150, 153, 157, 165-199 |
| W9159 | 286T9159 | | | PED POWER OUTLETS - MASTER CONTROL UNIT 115V AC IN | | | | | | | | | | | |
| 001 | 12 | PA | | | 45-10 | 25-25-23 | D01067E | | 1 | | D09299P | | 1 | | 150, 153, 157, 165-199 |
| 002 | 12 | PA | | | 45-10 | 25-25-23 | D01067E | | 2 | | D09299P | | 2 | | 150, 153, 157, 165-199 |
| 003 | 12 | PA | | | 45-10 | 25-25-23 | D01067E | | 3 | | D09299P | | 3 | | 150, 153, 157, 165-199 |
| 004 | 12 | PA | | | 45-10 | 25-25-23 | D01067E | | 4 | | GD09035 | A.. | E | | 150, 153, 157, 165-199 |
| 005 | 12 | PA | | | 45-10 | 25-25-23 | D01067E | | 5 | | GD09036 | D.. | E | | 150, 153, 157, 165-199 |
| 006 | 12 | PA | | | 45-10 | 25-25-23 | M09001 | =G | \$ | | GD09036 | D.. | E | | 150, 153, 157, 165-199 |

WIRE LIST

D280T132

91-21-11

Section W9150

Page 1 End

Mar 09/2006



767-200/300 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | To | | | | |
|--------------|----|-----------------|----|-----|------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9160 | | 286T9160 | | | PED POWER OUTLETS - CONTROL | | | | | | | | | | |
| 101 | 20 | PQ | A | | 20-0 | 25-25-23 | D01067F | 18 | | | D05710P | 12 | | | 150, 153, 157, 165-199 |
| 101Z | | | A | | 0-0 | 25-25-23 | D01067F | | | FA | D05710P | 13 | | | 150, 153, 157, 165-199 |
| 103 | 20 | PQ | C | | 45-10 | 25-25-23 | D01067F | 5 | | | D12206 | 11 | | | 150, 153, 157, 165-199 |
| 103Z | | | C | | 0-0 | 25-25-23 | D01067F | | | FA | D12206 | DED | | | 150, 153, 157, 165-199 |
| 104 | 20 | PQ | D | | 45-10 | 25-25-23 | D01067F | 2 | | * | D12206 | 10 | | | 150, 153, 157, 165-199 |
| 104Z | | | D | | 0-0 | 25-25-23 | D01067F | | | FA | D12206 | DED | | | 150, 153, 157, 165-199 |
| 105 | 20 | PQ | B | | 45-10 | 25-25-23 | D01067F | 20 | | * | D12206 | 12 | | | 150, 153, 157, 165-199 |
| 105Z | | | B | | 0-0 | 25-25-23 | D01067F | | | FA | D12206 | DED | | | 150, 153, 157, 165-199 |
| 106 | 20 | PQ | H | | 20-0 | 25-25-23 | D01067F | 20 | | * | D13444P | 10 | | | 150, 153, 157, 165-199 |
| 106Z | | | H | | 0-0 | 25-25-23 | D01067F | | | FA | D13444P | | | FB | 150, 153, 157, 165-199 |
| 107 | 20 | PQ | G | | 20-0 | 25-25-23 | D01067F | 4 | | | D13444P | 20 | | | 150, 153, 157, 165-199 |
| 107Z | | | G | | 0-0 | 25-25-23 | D01067F | | | FA | D13444P | | | FB | 150, 153, 157, 165-199 |
| 108 | 20 | PQ | J | | 20-0 | 25-25-23 | D01067F | 2 | | * | D13444P | 37 | | | 150, 153, 157, 165-199 |
| 108Z | | | J | | 0-0 | 25-25-23 | D01067F | | | FA | D13444P | | | FB | 150, 153, 157, 165-199 |
| 109 | 20 | PQ | E | | 20-0 | 25-25-23 | D12206 | 9 | | | D13444P | 19 | | | 150, 153, 157, 165-199 |
| 109Z | | | E | | 0-0 | 25-25-23 | D12206 | DED | | | D13444P | | | FB | 150, 153, 157, 165-199 |
| 110 | 20 | PQ | F | | 20-0 | 25-25-23 | D12206 | 8 | | | D13444P | 38 | | | 150, 153, 157, 165-199 |
| 110Z | | | F | | 0-0 | 25-25-23 | D12206 | DED | | | D13444P | | | FB | 150, 153, 157, 165-199 |
| FRA | | | | | 0-0 | 25-25-23 | D01067F | | | FA | D01067F | =CC | D | | 150, 153, 157, 165-199 |
| FRB | | | | | 0-0 | 25-25-23 | D13444P | 51 | | | D13444P | | | FB | 150, 153, 157, 165-199 |
| W9167 | | 286T9167 | | | PED POWER OUTLETS - CONTROL | | | | | | | | | | |
| 001 | 20 | PQ | A | | 10-0 | 25-25-23 | D05710J | 12 | | | D00144 | D1 | | | 150, 153, 157, 165-199 |
| 001Z | | | A | | 0-0 | 25-25-23 | D05710J | 13 | | | D00144 | DED | | | 150, 153, 157, 165-199 |
| 002 | 20 | PA | | | 10-0 | 25-25-23 | GDX0001 | D.. | 2 | | D00144 | D2 | | | 150, 153, 157, 165-199 |

WIRE LIST
D280T132

91-21-11
Section W9160
Page 1 End
Mar 09/2006



| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|--------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W9510 | 286T9510 | | | POTABLE WTR & LAV VACUUM WASTE SYSTEM | | | | | | | | | | | |
| 001 | 20 | | PA | | 1-0 | 38-32-11 | D01262 | | CAP | Y | GD03246 | D.. | E | * | 276 |
| 002 | 20 | | PA | | 1-0 | 38-32-11 | D00612 | | CAP | Y | GD03246 | D.. | E | * | 276 |