

# Cisco SPA2102 Phone Adapter with Router Cisco Small Business Voice Gateways and ATAs

Feature-Rich Voice Adapter for VoIP

### **Highlights**

- Enables high-quality, feature-rich voice-over-IP service through your broadband Internet connection
- Two standard phone ports for use with analog telephones or fax machines, with independent phone numbers
- · High-quality, clear-sounding voice service using advanced quality-of-service capability
- Compatible with common telephone features, such as caller ID, call waiting, call forwarding, and voicemail

Figure 1. Cisco SPA2012 Phone Adapter with Router



## **Product Overview**

Inexpensive, easy to install, and simple to use, the Cisco® SPA2102 Phone Adapter with Router (Figure 1) connects a standard telephone or fax machine to an IP-based data network. Voice over IP (VoIP) service providers can offer residential and business users traditional and enhanced communication services via the customer's broadband connection to the Internet.

The Cisco SPA2102 features two basic telephone ports to connect existing analog phones or fax machines to a private branch exchange (PBX) system. It also includes two 100BASE-T RJ-45 Ethernet interfaces to connect to a home or office LAN, as well as an Ethernet connection to connect a broadband modem or router (WAN). Each phone line can be configured independently via software controlled by the service provider or the end user. With the SPA2102, users are able to protect and extend their investment in their existing analog telephones, conference

speakerphones, and fax machines, as well as control their migration to IP with an extremely affordable, reliable solution.

Installed by the end user and remotely provisioned, configured, and maintained by the service provider, each Cisco SPA2102 converts voice traffic into data packets for transmission over an IP network. Compact in design, the SPA2102 can be used in consumer and business VoIP service offerings, including full-featured IP Centrex environments. The SPA2102 uses international standards for voice and data networking for reliable operation.

#### **Features**

- Toll-quality voice and carrier-grade feature support: The Cisco SPA2102 delivers clear, high-quality voice communication under a variety of network conditions. Excellent voice quality in challenging, changeable IP network environments is made possible via the advanced implementation of standard voice coding algorithms. The SPA2102 is interoperable with common telephony equipment such as fax, voicemail, PBX/KTS, and interactive voice response systems.
- Large-scale deployment and management: The Cisco SPA2102 enables service providers to
  provide customized services to their subscribers. It can be remotely provisioned and supports
  dynamic, in-service software upgrades. A highly secure profile upload saves providers the time
  and expense of managing and preconfiguring or reconfiguring customer premises equipment
  (CPE) for deployment.
- Ironclad security: The Cisco SPA2102 supports highly secure, encryption-based methods for communication, provisioning, and servicing.

#### **Specifications**

Table 1 contains the specifications and package contents for the Cisco SPA2012 Phone Adapter with Router.

Table 1. Specifications for the Cisco SPA2012 Phone Adapter with Router

# **Specifications** Data networking • MAC address (IEEE 802.3) • IPv4 (RFC 791) • Address Resolution Protocol (ARP) • DNS-A record (RFC 1706), SRV record (RFC 2782) • Dynamic Host Configuration Protocol (DHCP) client (RFC 2131) • DHCP server (RFC 2131) • Internet Control Message Protocol (ICMP) (RFC 792) • TCP (RFC 793) • User Datagram Protocol (UDP) (RFC 768) • Real Time Protocol (RTP) (RFC 1889, 1890) • Real Time Control Protocol (RTCP) (RFC 1889) • Differentiated Services (DiffServ) (RFC 2475), type of service (ToS) (RFC 791, 1349) • Simple Network Time Protocol (SNTP) (RFC 2030) • Upload data rate limiting: static and automatic • Quality of service (QoS): voice packet prioritization over other packet types • Router or bridge mode of operation • MAC address cloning · Port forwarding

Voice gateway	Session Initiation Protocol (SIP) v2 (RFC 3261, 3262, 3263, 3264)     SIP proxy redundancy-dynamic via DNS SRV, A records
	Reregistration with primary SIP proxy server
	SIP support in Network Address Translation (NAT) networks (including Serial Tunnel)
	[STUN])
	Highly secure (encrypted) calling via prestandard implementation of Secure RTP
Voice algorithms	Codec name assignment
	• G.711 (A-law and μ-law)
	• G.726 (16/24/32/40 kbps)
	• G.729 A
	• G.723.1 (6.3 kbps, 5.3 kbps)
	Dynamic payload
	Adjustable audio frames per packet
Voice specifications	Dual-tone multifrequency (DTMF): in-band and out-of-band (RFC 2833) (SIP info)
	Flexible dial plan support with interdigit timers and IP dialing
	Call progress tone generation
	Jitter buffer-adaptive
	• Frame loss concealment
	• Full duplex audio
	Echo cancellation (G.165/G.168)      Voice activity detector (VAR) with allower suppression
	Voice activity detection (VAD) with silence suppression     Attenuation/gain adjustments
	Flash hook timer
	Message waiting indicator (MWI) tones
	Visual message waiting indicator (VMWI) via frequency shift keying (FSK)
	Polarity control
	Hook flash event signaling
	Caller ID generation (name and number)-Bellcore, DTMF, European
	Telecommunications Standards Institute (ETSI)
	Music on hold client
	Streaming audio server-up to 10 sessions
Fax capability	Fax tone detection pass-through
	<ul> <li>Fax: G.711 pass-through or real-time fax over IP via T.38 (T.38 support is dependent or fax machine and network/transport resilience.)</li> </ul>
	, ,
Security	Password-protected system reset to factory default
	Password-protected administrator and user access authority
	Provisioning/configuration/authentication:
	LITTES with feature installed alient continues
	HTTPS with factory-installed client certificate     HTTP direct propertied outbonfication via MD5 (PEC 1321)
	HTTP digest-encrypted authentication via MD5 (RFC 1321)
	HTTP digest-encrypted authentication via MD5 (RFC 1321)     Up to 256-bit Advanced Encryption Standard (AES) encryption
Provisioning, administration, and maintenance	HTTP digest-encrypted authentication via MD5 (RFC 1321) Up to 256-bit Advanced Encryption Standard (AES) encryption Web browser administration and configuration via integral web server
	HTTP digest-encrypted authentication via MD5 (RFC 1321) Up to 256-bit Advanced Encryption Standard (AES) encryption  Web browser administration and configuration via integral web server Telephone keypad configuration with interactive voice prompts
	HTTP digest-encrypted authentication via MD5 (RFC 1321) Up to 256-bit Advanced Encryption Standard (AES) encryption Web browser administration and configuration via integral web server
	<ul> <li>HTTP digest-encrypted authentication via MD5 (RFC 1321)</li> <li>Up to 256-bit Advanced Encryption Standard (AES) encryption</li> <li>Web browser administration and configuration via integral web server</li> <li>Telephone keypad configuration with interactive voice prompts</li> <li>Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol</li> </ul>
	HTTP digest-encrypted authentication via MD5 (RFC 1321) Up to 256-bit Advanced Encryption Standard (AES) encryption  Web browser administration and configuration via integral web server Telephone keypad configuration with interactive voice prompts Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP)
	HTTP digest-encrypted authentication via MD5 (RFC 1321) Up to 256-bit Advanced Encryption Standard (AES) encryption  Web browser administration and configuration via integral web server Telephone keypad configuration with interactive voice prompts Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP) Asynchronous notification of upgrade availability via NOTIFY
	HTTP digest-encrypted authentication via MD5 (RFC 1321) Up to 256-bit Advanced Encryption Standard (AES) encryption  Web browser administration and configuration via integral web server Telephone keypad configuration with interactive voice prompts Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP) Asynchronous notification of upgrade availability via NOTIFY Nonintrusive, in-service upgrades
	HTTP digest-encrypted authentication via MD5 (RFC 1321) Up to 256-bit Advanced Encryption Standard (AES) encryption  Web browser administration and configuration via integral web server Telephone keypad configuration with interactive voice prompts Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP) Asynchronous notification of upgrade availability via NOTIFY Nonintrusive, in-service upgrades Report generation and event logging
	HTTP digest-encrypted authentication via MD5 (RFC 1321) Up to 256-bit Advanced Encryption Standard (AES) encryption  Web browser administration and configuration via integral web server Telephone keypad configuration with interactive voice prompts Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP) Asynchronous notification of upgrade availability via NOTIFY Nonintrusive, in-service upgrades Report generation and event logging Stats in BYE message
	<ul> <li>HTTP digest-encrypted authentication via MD5 (RFC 1321)</li> <li>Up to 256-bit Advanced Encryption Standard (AES) encryption</li> <li>Web browser administration and configuration via integral web server</li> <li>Telephone keypad configuration with interactive voice prompts</li> <li>Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP)</li> <li>Asynchronous notification of upgrade availability via NOTIFY</li> <li>Nonintrusive, in-service upgrades</li> <li>Report generation and event logging</li> <li>Stats in BYE message</li> <li>Syslog and debug server records-per-line configurable</li> </ul>
and maintenance	<ul> <li>HTTP digest-encrypted authentication via MD5 (RFC 1321)</li> <li>Up to 256-bit Advanced Encryption Standard (AES) encryption</li> <li>Web browser administration and configuration via integral web server</li> <li>Telephone keypad configuration with interactive voice prompts</li> <li>Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP)</li> <li>Asynchronous notification of upgrade availability via NOTIFY</li> <li>Nonintrusive, in-service upgrades</li> <li>Report generation and event logging</li> <li>Stats in BYE message</li> <li>Syslog and debug server records-per-line configurable</li> <li>Per-line and purpose configurable syslog and debug options</li> </ul>
and maintenance	<ul> <li>HTTP digest-encrypted authentication via MD5 (RFC 1321)</li> <li>Up to 256-bit Advanced Encryption Standard (AES) encryption</li> <li>Web browser administration and configuration via integral web server</li> <li>Telephone keypad configuration with interactive voice prompts</li> <li>Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP)</li> <li>Asynchronous notification of upgrade availability via NOTIFY</li> <li>Nonintrusive, in-service upgrades</li> <li>Report generation and event logging</li> <li>Stats in BYE message</li> <li>Syslog and debug server records-per-line configurable</li> <li>Per-line and purpose configurable syslog and debug options</li> <li>Two 100BASE-T RJ-45 Ethernet ports (IEEE 802.3)</li> </ul>
and maintenance	<ul> <li>HTTP digest-encrypted authentication via MD5 (RFC 1321)</li> <li>Up to 256-bit Advanced Encryption Standard (AES) encryption</li> <li>Web browser administration and configuration via integral web server</li> <li>Telephone keypad configuration with interactive voice prompts</li> <li>Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP)</li> <li>Asynchronous notification of upgrade availability via NOTIFY</li> <li>Nonintrusive, in-service upgrades</li> <li>Report generation and event logging</li> <li>Stats in BYE message</li> <li>Syslog and debug server records-per-line configurable</li> <li>Per-line and purpose configurable syslog and debug options</li> <li>Two 100BASE-T RJ-45 Ethernet ports (IEEE 802.3)</li> <li>2 RJ-11 FXS phone ports-for analog circuit telephone device (tip/ring)</li> </ul>
Physical interfaces Subscriber line interface	<ul> <li>HTTP digest-encrypted authentication via MD5 (RFC 1321)</li> <li>Up to 256-bit Advanced Encryption Standard (AES) encryption</li> <li>Web browser administration and configuration via integral web server</li> <li>Telephone keypad configuration with interactive voice prompts</li> <li>Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP)</li> <li>Asynchronous notification of upgrade availability via NOTIFY</li> <li>Nonintrusive, in-service upgrades</li> <li>Report generation and event logging</li> <li>Stats in BYE message</li> <li>Syslog and debug server records-per-line configurable</li> <li>Per-line and purpose configurable syslog and debug options</li> <li>Two 100BASE-T RJ-45 Ethernet ports (IEEE 802.3)</li> <li>2 RJ-11 FXS phone ports-for analog circuit telephone device (tip/ring)</li> <li>Ring waveform: trapezoidal and sinusoidal *</li> </ul>
Physical interfaces Subscriber line interface	<ul> <li>HTTP digest-encrypted authentication via MD5 (RFC 1321)</li> <li>Up to 256-bit Advanced Encryption Standard (AES) encryption</li> <li>Web browser administration and configuration via integral web server</li> <li>Telephone keypad configuration with interactive voice prompts</li> <li>Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP)</li> <li>Asynchronous notification of upgrade availability via NOTIFY</li> <li>Nonintrusive, in-service upgrades</li> <li>Report generation and event logging</li> <li>Stats in BYE message</li> <li>Syslog and debug server records-per-line configurable</li> <li>Per-line and purpose configurable syslog and debug options</li> <li>Two 100BASE-T RJ-45 Ethernet ports (IEEE 802.3)</li> <li>2 RJ-11 FXS phone ports-for analog circuit telephone device (tip/ring)</li> <li>Ring waveform: trapezoidal and sinusoidal *</li> <li>Maximum ringer load: 3 ringer equivalence numbers (RENs)</li> </ul>
Physical interfaces Subscriber line interface	<ul> <li>HTTP digest-encrypted authentication via MD5 (RFC 1321)</li> <li>Up to 256-bit Advanced Encryption Standard (AES) encryption</li> <li>Web browser administration and configuration via integral web server</li> <li>Telephone keypad configuration with interactive voice prompts</li> <li>Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP)</li> <li>Asynchronous notification of upgrade availability via NOTIFY</li> <li>Nonintrusive, in-service upgrades</li> <li>Report generation and event logging</li> <li>Stats in BYE message</li> <li>Syslog and debug server records-per-line configurable</li> <li>Per-line and purpose configurable syslog and debug options</li> <li>Two 100BASE-T RJ-45 Ethernet ports (IEEE 802.3)</li> <li>2 RJ-11 FXS phone ports-for analog circuit telephone device (tip/ring)</li> <li>Ring waveform: trapezoidal and sinusoidal *</li> <li>Maximum ringer load: 3 ringer equivalence numbers (RENs)</li> <li>On-hook/off-hook characteristics:</li> </ul>
Physical interfaces Subscriber line interface	<ul> <li>HTTP digest-encrypted authentication via MD5 (RFC 1321)</li> <li>Up to 256-bit Advanced Encryption Standard (AES) encryption</li> <li>Web browser administration and configuration via integral web server</li> <li>Telephone keypad configuration with interactive voice prompts</li> <li>Automated provisioning and upgrade via HTTPS, HTTP, Trivial File Transfer Protocol (TFTP)</li> <li>Asynchronous notification of upgrade availability via NOTIFY</li> <li>Nonintrusive, in-service upgrades</li> <li>Report generation and event logging</li> <li>Stats in BYE message</li> <li>Syslog and debug server records-per-line configurable</li> <li>Per-line and purpose configurable syslog and debug options</li> <li>Two 100BASE-T RJ-45 Ethernet ports (IEEE 802.3)</li> <li>2 RJ-11 FXS phone ports-for analog circuit telephone device (tip/ring)</li> <li>Ring waveform: trapezoidal and sinusoidal *</li> <li>Maximum ringer load: 3 ringer equivalence numbers (RENs)</li> <li>On-hook/off-hook characteristics:</li> <li>On-hook voltage (tip/ring): -50V nominal</li> </ul>

Regulatory compliance	• FCC (Part 15, Class B) , CE, ICES-003	
Power supply	Switching type (100–240V) automatic	
	DC input voltage: +5V DC at 2.0A maximum	
	Power consumption: 5W	
	<ul> <li>Power adapter: 100–240V, 50–60 Hz (26–34VA) AC input, 1.8-m cord</li> </ul>	
Indicator lights/LED	Power, Internet, Phone 1, Phone 2	
Documentation	Quick-start installation guide	
	Administration guide-service providers only	
	Provisioning guide-service providers only	
Package Contents		
Cisco SPA2012 Phone Adapter with Router		
5V power adapter		
RJ-45 Ethernet cable		
Quick installation guide		
Environmental		
Dimensions	3.98 x 3.98. x 1.10 in.	
WxHxD	(101 x 101 x 28 mm)	
Unit weight	5.29 oz (0.15 kg)	
Operating temperature	32°~113°F (0°~45°C)	
Storage temperature	-13°~185°F (-25°~85°C)	
Operating humidity	10%~90% noncondensing	
Storage humidity	10%~90% noncondensing	
Product Warranty		
1-year limited hardware warranty with return to factory replacement and 90-day limited software warranty		

<sup>\*</sup> Note: Many specifications are programmable within a defined range or list of options. Please see the Administration Guide for details. The configuration profile is uploaded to the Cisco SPA2102 at the time of provisioning.

# Cisco Limited Warranty for Cisco Small Business Series Products

This Cisco Small Business product comes with a 1-year limited hardware warranty with return to factory replacement and a 90-day limited software warranty. In addition, Cisco offers software application updates for bug fixes and telephone technical support at no charge for the first 12 months following the date of purchase. To download software updates, go to: <a href="http://www.cisco.com/go/smallbiz">http://www.cisco.com/go/smallbiz</a>.

Product warranty terms and other information applicable to Cisco products are available at <a href="http://www.cisco.com/go/warranty">http://www.cisco.com/go/warranty</a>.

# For More Information

For more information on Cisco Small Business products and solutions, visit: <a href="http://www.cisco.com/smallbusiness">http://www.cisco.com/smallbusiness</a>.



Americas Headquarters Cisco Systems, Inc. San Jose, CA Asia Pacific Headquarters Cisco Systems (USA) Pte. Ltd. Singapore Europe Headquarters Cisco Systems International BV Amsterdam, The Netherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at www.cisco.com/go/offices.

CCDE, CCENT, Cisco Eos, Cisco Lumin, Cisco Nexus, Cisco StadiumVision, Cisco TelePresence, Cisco WebEx, the Cisco logo, DCE, and Welcome to the Human Network are trademarks; Changing the Way We Work, Live, Play, and Learn and Cisco Store are service marks; and Access Registrar, Aironet, AsyncOS, Bringing the Meeting To You, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, CCVP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco OloS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Collaboration Without Limitation, EtherFast, EtherSwitch, Event Center, Fast Step, Follow Me Browsing, FormShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, iQuick Study, IronPort, the IronPort logo, LightStream, Linksys, MediaTone, MeetingPlace, MeetingPlace Chime Sound, MGX, Networkers, Networking Academy, Network Registrar, PCNow, PIX, PowerPanels, ProConnect, ScriptShare, SenderBase, SMARTnet, Spectrum Expert, StackWise, The Fastest Way to Increase Your Internet Quotient, TransPath, WebEx, and the WebEx logo are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0809R)

Printed in USA C78-502137-00 11/08