



# Agilent 34980A Multifunction Switch/Measure Unit Command Quick Reference

Version 1.2

## Syntax Conventions

- Braces ( { } ) enclose the parameter choices for a given command string. The braces are not sent with the command string.
- A vertical bar ( | ) separates multiple parameter choices for a given command string.
- Triangle brackets ( < > ) indicate that you must specify a value for the enclosed parameter. The brackets are not sent with the command string. You must specify a value for the parameter (e.g., "VOLT:DC:RANG 10").
- Some parameters are enclosed in square brackets ( [ ] ). The square brackets indicate that the parameter is optional and can be omitted. The brackets are not sent with the command string. If you do not specify a value for an optional parameter, the instrument chooses a default value.

## Measurement Commands

```
MEASure:CURRent:AC? [{<range>|AUTO|MINIMAX|DEF} [, {<resolution>|MINIMAX|DEF} ] , ] [(@<ch_list>)]
MEASure:CURRent[:DC]? [{<range>|AUTO|MINIMAX|DEF} [, {<resolution>|MINIMAX|DEF} ] , ] [(@<ch_list>)]
MEASure:DIGital? {BYTE|1|WORD|2|LWORD|4}, [<voltage>], [{NORMAl|INVerted} , ] (@<ch_list>)
MEASure:FREQuency? [{<range>|MINIMAX|DEF} [, {<resolution>|MINIMAX|DEF} ] , ] [(@<ch_list>)]
MEASure:FRESistance? [{<range>|AUTO|MINIMAX|DEF} [, {<resolution>|MINIMAX|DEF} ] , ] [(@<ch_list>)]
MEASure:PERiod? [{<range>|MINIMAX|DEF} [, {<resolution>|MINIMAX|DEF} ] , ] [(@<ch_list>)]
MEASure:RESistance? [{<range>|AUTO|MINIMAX|DEF} [, {<resolution>|MINIMAX|DEF} ] , ] [(@<ch_list>)]
MEASure:TEMPerature? {TCouple|RTD|FRTD|THERmistor|DEF}, {<type>|DEF} [, 1 [, {<resolution>|MINIMAX|DEF} ] ]
  [, (@<ch_list>)]
MEASure:TOTALize? [{READ|IRRESet} , ] (@<ch_list>)
MEASure[:VOLTage]:AC? [{<range>|AUTO|MINIMAX|DEF} [, {<resolution>|MINIMAX|DEF} ] , ] [(@<ch_list>)]
MEASure[:VOLTage][:DC]? [{<range>|AUTO|MINIMAX|DEF} [, {<resolution>|MINIMAX|DEF} ] , ] [(@<ch_list>)]
```

## Temperature Configuration Commands

```
CONFigure:TEMPerature {TCouple|RTD|FRD|THERmistor|DEF}, {<type>|DEF} [,1 [, {<resolution>|MINIMAX|DEF} ] ]  
[, (@<ch_list>)]  
CONFigure? [(@<ch_list>)]
```

```
[SENSe:]TEMPerature:APERture {<seconds>|MINIMAX|DEF} [, (@<ch_list>)]  
[SENSe:]TEMPerature:APERture? [({@<ch_list>}|MINIMAX)]
```

```
[SENSe:]TEMPerature:APERture:ENABled? [(@<ch_list>)]
```

```
[SENSe:]TEMPerature:NPLC {<PLCs>|MINIMAX|DEF} [, (@<ch_list>)]  
[SENSe:]TEMPerature:NPLC? [({@<ch_list>}|MINIMAX)]
```

```
[SENSe:]TEMPerature:TRANsdncer:TYPE {TCouple|RTD|FRD|THERmistor} [, (@<ch_list>)]  
[SENSe:]TEMPerature:TRANsdncer:TYPE? [(@<ch_list>)]
```

```
[SENSe:]TEMPerature:ZERO:AUTO {OFF|O|ON|1} [, (@<ch_list>)]  
[SENSe:]TEMPerature:ZERO:AUTO? [(@<ch_list>)]
```

```
UNIT:TEMPerature {C|F|K} [, (@<ch_list>)]  
UNIT:TEMPerature? [(@<ch_list>)]
```

### Thermocouple Configuration

```
[SENSe:]TEMPerature:RJUNction[:|INTernal]? (@<ch_list>)
```

```
[SENSe:]TEMPerature:TRANsdncer:TCouple:CHECK {OFF|O|ON|1} [, (@<ch_list>)]  
[SENSe:]TEMPerature:TRANsdncer:TCouple:CHECK? [(@<ch_list>)]
```

```
[SENSe:]TEMPerature:TRANsdncer:TCouple:IMPedance:AUTO  
[SENSe:]TEMPerature:TRANsdncer:TCouple:IMPedance:AUTO?
```

```
[SENSe:]TEMPerature:TRANsdncer:TCouple:RJUNction {<temperature>|MINIMAX|DEF} [, (@<ch_list>)]  
[SENSe:]TEMPerature:TRANsdncer:TCouple:RJUNction? [({@<ch_list>}|MINIMAX)]
```

```
[SENSe:]TEMPerature:TRANsdncer:TCouple:RJUNction:EXTernal?
```

```
[SENSe:]TEMPerature:TRANsdncer:TCouple:RJUNction:TYPE {EXTernal|FIXed|INTernal} [, (@<ch_list>)]  
[SENSe:]TEMPerature:TRANsdncer:TCouple:RJUNction:TYPE? [(@<ch_list>)]
```

```
[SENSe:]TEMPerature:TRANsdncer:TCouple:TYPE {B|E|J|K|N|IR|S|IT} [, (@<ch_list>)]  
[SENSe:]TEMPerature:TRANsdncer:TCouple:TYPE? [(@<ch_list>)]
```

## RTD Configuration

```
[SENSe:]TEMPerature:TRANSDUCER:FRTD:OCOMPensated {OFF|O|ON|1} [, (@<ch_list>)]
[SENSe:]TEMPerature:TRANSDUCER:FRTD:OCOMPensated? [(@<ch_list>)]

[SENSe:]TEMPerature:TRANSDUCER:FRTD:REFerence {OFF|O|ON|1} [, (@<ch_list>)]
[SENSe:]TEMPerature:TRANSDUCER:FRTD:REFerence? [(@<ch_list>)]

[SENSe:]TEMPerature:TRANSDUCER:FRTD:RESistance[:REFerence] {<reference>|MINIMAX|DEF} [, (@<ch_list>)]
[SENSe:]TEMPerature:TRANSDUCER:FRTD:RESistance[:REFerence]? [({@<ch_list>}|MINIMAX)]

[SENSe:]TEMPerature:TRANSDUCER:FRTD:TYPE {85|91} [, (@<ch_list>)]
[SENSe:]TEMPerature:TRANSDUCER:FRTD:TYPE? [(@<ch_list>)]

[SENSe:]TEMPerature:TRANSDUCER:RTD:OCOMPensated {OFF|O|ON|1} [, (@<ch_list>)]
[SENSe:]TEMPerature:TRANSDUCER:RTD:OCOMPensated? [(@<ch_list>)]

[SENSe:]TEMPerature:TRANSDUCER:RTD:REFerence {OFF|O|ON|1} [, (@<ch_list>)]
[SENSe:]TEMPerature:TRANSDUCER:RTD:REFerence? [(@<ch_list>)]

[SENSe:]TEMPerature:TRANSDUCER:RTD:RESistance[:REFerence] {<reference>|MINIMAX|DEF} [, (@<ch_list>)]
[SENSe:]TEMPerature:TRANSDUCER:RTD:RESistance[:REFerence]? [({@<ch_list>}|MINIMAX)]

[SENSe:]TEMPerature:TRANSDUCER:RTD:TYPE {85|91} [, (@<ch_list>)]
[SENSe:]TEMPerature:TRANSDUCER:RTD:TYPE? [(@<ch_list>)]
```

## Thermistor Configuration

```
[SENSe:]TEMPerature:TRANSDUCER:THERMISTOR:REFerence {OFF|O|ON|1} [, (@<ch_list>)]
[SENSe:]TEMPerature:TRANSDUCER:THERMISTOR:REFerence? [(@<ch_list>)]

[SENSe:]TEMPerature:TRANSDUCER:THERMISTOR:TYPE {2252|5000|10000} [, (@<ch_list>)]
[SENSe:]TEMPerature:TRANSDUCER:THERMISTOR:TYPE? [(@<ch_list>)]
```

## Voltage Configuration Commands

### DC Voltage Configuration

CONFigure[:VOLTage][:DC] [{<range>|AUTO|MINIMAXIDEF} [, {<resolution>|MINIMAXIDEF}] , ] [(@<ch\_list>)]  
CONFigure? [(@<ch\_list>)]

[SENSe:]VOLTage[:DC]:APERture {<seconds>|MINIMAXIDEF} [, (@<ch\_list>)]

[SENSe:]VOLTage[:DC]:APERture? [(@<ch\_list>)|MINIMAX]

[SENSe:]VOLTage[:DC]:APERture:ENABLEd? [(@<ch\_list>)]

[SENSe:]VOLTage[:DC]:IMPedance:AUTO {OFF|0|ON|1} [, (@<ch\_list>)]

[SENSe:]VOLTage[:DC]:IMPedance:AUTO? [(@<ch\_list>)]

[SENSe:]VOLTage[:DC]:NPLC {<PLCs>|MINIMAXIDEF} [, (@<ch\_list>)]

[SENSe:]VOLTage[:DC]:NPLC? [(@<ch\_list>)|MINIMAX]

[SENSe:]VOLTage[:DC]:RANGe {<range>|MINIMAXIDEF} [, (@<ch\_list>)]

[SENSe:]VOLTage[:DC]:RANGe? [(@<ch\_list>)|MINIMAX]

[SENSe:]VOLTage[:DC]:RANGe:AUTO {OFF|0|ON|1} [, (@<ch\_list>)]

[SENSe:]VOLTage[:DC]:RANGe:AUTO? [(@<ch\_list>)]

[SENSe:]VOLTage[:DC]:RESolution {<resolution>|MINIMAXIDEF} [, (@<ch\_list>)]

[SENSe:]VOLTage[:DC]:RESolution? [(@<ch\_list>)|MINIMAX]

[SENSe:]VOLTage[:DC]:ZERO:AUTO {OFF|0|ON|1} [, (@<ch\_list>)]

[SENSe:]VOLTage[:DC]:ZERO:AUTO? [(@<ch\_list>)]

### AC Voltage Configuration

CONFigure[:VOLTage]:AC [{<range>|AUTO|MINIMAXIDEF} [, {<resolution>|MINIMAXIDEF}] , ] [(@<ch\_list>)]

CONFigure? [(@<ch\_list>)]

[SENSe:]VOLTage:AC:BANDwidth {3|20|200|MINIMAXIDEF} [, (@<ch\_list>)]

[SENSe:]VOLTage:AC:BANDwidth? [(@<ch\_list>)|MINIMAX]

[SENSe:]VOLTage:AC:RANGe {<range>|MINIMAXIDEF} [, (@<ch\_list>)]

[SENSe:]VOLTage:AC:RANGe? [(@<ch\_list>)|MINIMAX]

[SENSe:]VOLTage:AC:RANGe:AUTO {OFF|0|ON|1} [, (@<ch\_list>)]

[SENSe:]VOLTage:AC:RANGe:AUTO? [(@<ch\_list>)]

## Resistance Configuration Commands

### 2-Wire Resistance Configuration

CONFigure:RESistance [{<range>|AUTO|MINIMAXIDEF} [, {<resolution>|MINIMAXIDEF}] , ] [(@<ch\_list>)]  
CONFigure? [(@<ch\_list>)]

[SENSe:]RESistance:APERture {<seconds>|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]RESistance:APERture? [(@<ch\_list>)|MINIMAX]

[SENSe:]RESistance:APERture:ENABLEd? [(@<ch\_list>)]

[SENSe:]RESistance:NPLC {<PLCs>|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]RESistance:NPLC? [(@<ch\_list>)|MINIMAX]

[SENSe:]RESistance:OCOMpensated {OFF|O|ON|1} [, (@<ch\_list>)]  
[SENSe:]RESistance:OCOMpensated? [(@<ch\_list>)]

[SENSe:]RESistance:RANGe {<range>|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]RESistance:RANGe? [(@<ch\_list>)|MINIMAX]

[SENSe:]RESistance:RANGe:AUTO {OFF|O|ON|1} [, (@<ch\_list>)]  
[SENSe:]RESistance:RANGe:AUTO? [(@<ch\_list>)]

[SENSe:]RESistance:RESolution {<resolution>|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]RESistance:RESolution? [(@<ch\_list>)|MINIMAX]

[SENSe:]RESistance:ZERO:AUTO {OFF|O|ON|1} [, (@<ch\_list>)]  
[SENSe:]RESistance:ZERO:AUTO? [(@<ch\_list>)]

### 4-Wire Resistance Configuration

CONFigure:FRESistance [{<range>|AUTO|MINIMAXIDEF} [, {<resolution>|MINIMAXIDEF}] , ] [(@<ch\_list>)]  
CONFigure? [(@<ch\_list>)]

[SENSe:]FRESistance:APERture {<seconds>|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]FRESistance:APERture? [(@<ch\_list>)|MINIMAX]

[SENSe:]FRESistance:APERture:ENABLEd? [(@<ch\_list>)]

[SENSe:]FRESistance:NPLC {<PLCs>|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]FRESistance:NPLC? [(@<ch\_list>)|MINIMAX]

[SENSe:]FRESistance:OCOMpensated {OFF|O|ON|1} [, (@<ch\_list>)]  
[SENSe:]FRESistance:OCOMpensated? [(@<ch\_list>)]

[SENSe:]FRESistance:RANGe {<range>|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]FRESistance:RANGe? [(@<ch\_list>)|MINIMAX]

[SENSe:]FRESistance:RANGe:AUTO {OFF|O|ON|1} [, (@<ch\_list>)]  
[SENSe:]FRESistance:RANGe:AUTO? [(@<ch\_list>)]

[SENSe:]FRESistance:RESolution {<resolution>|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]FRESistance:RESolution? [(@<ch\_list>)|MINIMAX]

## Current Configuration Commands

### DC Current Configuration

CONFigure:CURRent[:DC] [{<range>|AUTO|MINIMAX|DEF} [, {<resolution>|MINIMAX|DEF}] , ] [(@<ch\_list>)]  
CONFigure? [(@<ch\_list>)]

[SENSe:]CURRent[:DC]:APERture {<seconds>|MINIMAX|DEF} [, (@<ch\_list>)]  
[SENSe:]CURRent[:DC]:APERture? [{(@<ch\_list>)|MINIMAX}]

[SENSe:]CURRent[:DC]:APERture:ENABLEd? [(@<ch\_list>)]

[SENSe:]CURRent[:DC]:NPLC {<PLCs>|MINIMAX|DEF} [, (@<ch\_list>)]  
[SENSe:]CURRent[:DC]:NPLC? [{(@<ch\_list>)|MINIMAX}]

[SENSe:]CURRent[:DC]:RANGe {<range>|MINIMAX|DEF} [, (@<ch\_list>)]  
[SENSe:]CURRent[:DC]:RANGe? [{(@<ch\_list>)|MINIMAX}]

[SENSe:]CURRent[:DC]:RANGe:AUTO {OFF|0|ON|1} [, (@<ch\_list>)]  
[SENSe:]CURRent[:DC]:RANGe:AUTO? [(@<ch\_list>)]

[SENSe:]CURRent[:DC]:RESolution {<resolution>|MINIMAX|DEF} [, (@<ch\_list>)]  
[SENSe:]CURRent[:DC]:RESolution? [{(@<ch\_list>)|MINIMAX}]

[SENSe:]CURRent[:DC]:ZERO:AUTO {OFF|0|ON|1} [, (@<ch\_list>)]  
[SENSe:]CURRent[:DC]:ZERO:AUTO? [(@<ch\_list>)]

### AC Current Configuration

CONFigure:CURRent:AC [{<range>|AUTO|MINIMAX|DEF} [, {<resolution>|MINIMAX|DEF}] , ] [(@<ch\_list>)]  
CONFigure? [(@<ch\_list>)]

[SENSe:]CURRent:AC:BANDwidth {3|20|200|MINIMAX|DEF} [, (@<ch\_list>)]  
[SENSe:]CURRent:AC:BANDwidth? [{(@<ch\_list>)|MINIMAX}]

[SENSe:]CURRent:AC:RANGe {<range>|MINIMAX|DEF} [, (@<ch\_list>)]  
[SENSe:]CURRent:AC:RANGe? [{(@<ch\_list>)|MINIMAX}]

[SENSe:]CURRent:AC:RANGe:AUTO {OFF|0|ON|1} [, (@<ch\_list>)]  
[SENSe:]CURRent:AC:RANGe:AUTO? [(@<ch\_list>)]

## Frequency and Period Configuration Commands

### Frequency Configuration

CONFigure:FREQUency [{<range>|MINIMAXIDEF} [{<resolution>|MINIMAXIDEF}] , ] [(@<ch\_list>)]  
CONFigure? [(@<ch\_list>)]

[SENSe:]FREQUency:APERture {<seconds>|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]FREQUency:APERture? [(@<ch\_list>)|MINIMAX]

[SENSe:]FREQUency:RANGe:LOWer {<timeout>|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]FREQUency:RANGe:LOWer? [(@<ch\_list>)|MINIMAX]

[SENSe:]FREQUency:VOLTagE:RANGe {<voltage\_range>|AUTO|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]FREQUency:VOLTagE:RANGe? [(@<ch\_list>)|MINIMAX]

[SENSe:]FREQUency:VOLTagE:RANGe:AUTO {OFF|0|ON|1} [, (@<ch\_list>)]  
[SENSe:]FREQUency:VOLTagE:RANGe:AUTO? [(@<ch\_list>)]

### Period Configuration

CONFigure:PERiod [{<range>|MINIMAXIDEF} [{<resolution>|MINIMAXIDEF}] , ] [(@<ch\_list>)]  
CONFigure? [(@<ch\_list>)]

[SENSe:]PERiod:APERture {<seconds>|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]PERiod:APERture? [(@<ch\_list>)|MINIMAX]

[SENSe:]PERiod:VOLTagE:RANGe {<voltage\_range>|MINIMAXIDEF} [, (@<ch\_list>)]  
[SENSe:]PERiod:VOLTagE:RANGe? [(@<ch\_list>)|MINIMAX]

[SENSe:]PERiod:VOLTagE:RANGe:AUTO {OFF|0|ON|1} [, (@<ch\_list>)]  
[SENSe:]PERiod:VOLTagE:RANGe:AUTO? [(@<ch\_list>)]

## Digital I/O and Totalizer Configuration Commands

### Digital I/O Configuration

CONFigure:DIGital {BYTE|1|WORD|2|LWORD|4}, [<voltage>], [{NORM|INVERTed}], (@<ch\_list>)

CONFigure:DIGital:DIRection {INPut|0|OUTPut|1}, (@<ch\_list>)  
CONFigure:DIGital:DIRection? (@<ch\_list>)

CONFigure:DIGital:HANDshake SYNChronous, [<thresh\_voltage>, [<level\_voltage>, [<polarity>],]] (@<ch\_list>)

CONFigure:DIGital:HANDshake:CTIME {<seconds>|MINIMAXIDEF}, (@<ch\_list>)  
CONFigure:DIGital:HANDshake:CTIME? [{MINIMAX},] (@<ch\_list>)

CONFigure:DIGital:HANDshake:DRIVE {ACTive|OCOLlector}, (@<ch\_list>)  
CONFigure:DIGital:HANDshake:DRIVE? (@<ch\_list>)

CONFigure:DIGital:HANDshake:POLarity {NORM|INVERTed}, [{H0|0|H1|1|H2|2|ALL},] (@<ch\_list>)  
CONFigure:DIGital:HANDshake:POLarity? {H0|0|H1|1|H2|2}, (@<ch\_list>)

CONFigure:DIGital:HANDshake:RATE {<frequency>|MINIMAXIDEF}, (@<ch\_list>)  
CONFigure:DIGital:HANDshake:RATE? [{MINIMAX},] (@<ch\_list>)

CONFigure:DiGital:HANDshake:STATe {HIMPedancelOFFION}, (@ <ch\_list>)  
 CONFigure:DiGital:HANDshake:STATe? (@ <ch\_list>)

CONFigure:DiGital:HANDshake:SYNChronous:STRobe[SOURce] {INTernal|EXTernal}, (@ <ch\_list>)  
 CONFigure:DiGital:HANDshake:SYNChronous:STRobe[SOURce]? (@ <ch\_list>)

CONFigure:DiGital:INTerrupt:POLarity {NORMal|INVerted}, (@ <ch\_list>)  
 CONFigure:DiGital:INTerrupt:POLarity? (@ <ch\_list>)

CONFigure:DiGital:POLarity {NORMal|INVerted}, (@ <ch\_list>)  
 CONFigure:DiGital:POLarity? (@ <ch\_list>)

CONFigure:DiGital:WIDTh {BYTE|1|WORD|2|LWORD|4}, (@ <ch\_list>)  
 CONFigure:DiGital:WIDTh? (@ <ch\_list>)

[SENSe:]DiGital:DATA[:{BYTE|1|WORD|2|LWORD|4}]? [{DECimal|BINary|HEXadecimal|OCTal},] (@ <ch\_list>)  
 [SENSe:]DiGital:DATA:BIT? <bit>, (@ <ch\_list>)

[SENSe:]DiGital:HANDshake:THReshold {<voltage>|MINIMAX|DEF}, (@ <ch\_list>)  
 [SENSe:]DiGital:HANDshake:THReshold? [{MINIMAX},] (@ <ch\_list>)

[SENSe:]DiGital:INTerrupt[:ENABLE] {OFF|O|ON|1}, (@ <ch\_list>)  
 [SENSe:]DiGital:INTerrupt[:ENABLE]? (@ <ch\_list>)

[SENSe:]DiGital:INTerrupt:MODE {MFUL|ICOMPare}, (@ <ch\_list>)  
 [SENSe:]DiGital:INTerrupt:MODE? (@ <ch\_list>)

[SENSe:]DiGital:INTerrupt:STATus? (@ <ch\_list>)

SOURce:DiGital:DATA[:{BYTE|1|WORD|2|LWORD|4}] <data>, (@ <ch\_list>)  
 SOURce:DiGital:DATA[:{BYTE|1|WORD|2|LWORD|4}]? [{DECimal|BINary|HEXadecimal|OCTal},] (@ <ch\_list>)

SOURce:DiGital:DATA:BIT {0|1}, <bit>, (@ <ch\_list>)  
 SOURce:DiGital:DATA:BIT? <bit>, (@ <ch\_list>)

SOURce:DiGital:DRIVE {ACTive|OCOLlector}, (@ <ch\_list>)  
 SOURce:DiGital:DRIVE? (@ <ch\_list>)

SOURce:DiGital:HANDshake:LEVel {<voltage>|MINIMAX|DEF}, (@ <ch\_list>)  
 SOURce:DiGital:HANDshake:LEVel? [{MINIMAX},] (@ <ch\_list>)

SOURce:DiGital:INTerrupt[:ENABLE] {OFF|O|ON|1}, (@ <ch\_list>)  
 SOURce:DiGital:INTerrupt[:ENABLE]? (@ <ch\_list>)

[SENSe:]DiGital:INTerrupt:MODE {START|STOP|GATE}, (@ <ch\_list>)  
 [SENSe:]DiGital:INTerrupt:MODE? (@ <ch\_list>)

[SENSe:]DiGital:MEMory:CLEar (@ <ch\_list>)

[SENSe:]DiGital:MEMory:COMPare:ACTion {CONTInue|START|STOP}, (@ <ch\_list>)  
 [SENSe:]DiGital:MEMory:COMPare:ACTion? (@ <ch\_list>)

[SENSe:]DiGital:MEMory[:DATA]? <index>, <count>, (@ <channel>)

[SENSe:]DiGital:MEMory[:DATA]:ALL? (@ <channel>)

[SENSe:]DiGital:MEMory[:DATA]:FORMat {LIST|BLOCK}, (@ <channel>)  
 [SENSe:]DiGital:MEMory[:DATA]:FORMat? (@ <channel>)



[SENSe:]DIGital:MEMory[:DATA]:POINts? [MAX,] (@<ch\_list>)

[SENSe:]DIGital:MEMory:ENABle {OFF|O|ON|1}, (@<ch\_list>)

[SENSe:]DIGital:MEMory:ENABle? (@<ch\_list>)

[SENSe:]DIGital:MEMory:MATCh[:DATA]? (@<ch\_list>)

[SENSe:]DIGital:MEMory:SAMPle:COUNT {<count>|MIN|MAX|DEF|INFINITY}, (@<ch\_list>)

[SENSe:]DIGital:MEMory:STARt (@<ch\_list>)

[SENSe:]DIGital:MEMory:STEP (@<ch\_list>)

[SENSe:]DIGital:MEMory:STOP (@<ch\_list>)

SOURce:DIGital:MEMory:TRACe <name>, (@<channel>)

SOURce:DIGital:MEMory:TRACe? (@<channel>)

[SENSe:]DIGital:THReshold {<voltage>|MIN|MAX|DEF}, (@<ch\_list>)

[SENSe:]DIGital:THReshold? [{MIN|MAX},] (@<ch\_list>)

SOURce:DIGital:LEVel {<voltage>|MIN|MAX|DEF}, (@<ch\_list>)

SOURce:DIGital:LEVel? [{MIN|MAX},] (@<ch\_list>)

SOURce:DIGital:MEMory:ABORt (@<ch\_list>)

SOURce:DIGital:MEMory:ENABle {OFF|O|ON|1}, (@<ch\_list>)

SOURce:DIGital:MEMory:ENABle? (@<ch\_list>)

SOURce:DIGital:MEMory:NCYCles {<count>|MIN|MAX|DEF|INFINITY}, (@<ch\_list>)

SOURce:DIGital:MEMory:NCYCles? [{MIN|MAX},] (@<ch\_list>)

SOURce:DIGital:MEMory:STARt (@<ch\_list>)

SOURce:DIGital:MEMory:STEP (@<ch\_list>)

SOURce:DIGital:MEMory:STOP (@<ch\_list>)

SOURce:DIGital:STATe {OFF|O|ON|1}, (@<ch\_list>)

SOURce:DIGital:STATe? (@<ch\_list>)

### Trace Pattern Configuration

TRACe:CATalog? {(@<channel>)|<slot>}

TRACe[:DATA]:DIGital[:{BYTE|1|WORD|2|LWORD|4}] (@<channel>), <name>, {<binary\_block>|<value>, <value> [<value>, ...]}

TRACe[:DATA]:DIGital:FUNCTion (@<channel>), {COUNT|WONes}, <name>, <points>

TRACe:DELete:ALL {(@<channel>)|<slot>}

TRACe:DELete[:NAME] {(@<channel>)|<slot>}, <name>

TRACe:FREE? {(@<channel>)|<slot>}

TRACe:POINts? {(@<channel>)|<slot>}, <name>

## Digital Input Pattern Comparison

CALCulate:COMPare:DATA[:{BYTE|1|WORD|2|LWORD|4}] <data>, (@ <ch\_list>)  
CALCulate:COMPare:DATA? (@ <ch\_list>)  
CALCulate:COMPare:MASK[:{BYTE|1|WORD|2|LWORD|4}] <data>, (@ <ch\_list>)  
CALCulate:COMPare:MASK? (@ <ch\_list>)  
CALCulate:COMPare:STATe {OFF|0|ON|1}, (@ <ch\_list>)  
CALCulate:COMPare:STATe? (@ <ch\_list>)  
CALCulate:COMPare:TYPE {EQUAl|NEQual}, (@ <ch\_list>)  
CALCulate:COMPare:TYPE? (@ <ch\_list>)  
[SENSe:]DIGital:MEMory:COMPare:ACTion {CONTInue|START|STOP}, (@ <ch\_list>)  
[SENSe:]DIGital:MEMory:COMPare:ACTion? (@ <ch\_list>)  
[SENSe:]DIGital:MEMory:MATCH[:DATA]? (@ <ch\_list>)

## Totalizer Configuration

CONFigure:COUNter:DCYCLE [{<gate\_time>|MIN|MAX|DEF},] (@ <ch\_list>)  
CONFigure:COUNter:FREQUENCY [{<gate\_time>|MIN|MAX|DEF},] (@ <ch\_list>)  
CONFigure:COUNter:PERiod [{<gate\_time>|MIN|MAX|DEF},] (@ <ch\_list>)  
CONFigure:COUNter:PWIDth [{<gate\_time>|MIN|MAX|DEF},] (@ <ch\_list>)  
CONFigure:COUNter:TOTalize [{READ|IRRESet},] (@ <ch\_list>)  
CONFigure:TOTalize [{READ|IRRESet},] (@ <ch\_list>)  
MEASure:COUNter:DCYCLE? [{<gate\_time>|MIN|MAX|DEF},] (@ <ch\_list>)  
MEASure:COUNter:FREQUENCY? [{<gate\_time>|MIN|MAX|DEF},] (@ <ch\_list>)  
MEASure:COUNter:PERiod? [{<gate\_time>|MIN|MAX|DEF},] (@ <ch\_list>)  
MEASure:COUNter:PWIDth? [{<gate\_time>|MIN|MAX|DEF},] (@ <ch\_list>)  
MEASure:COUNter:TOTalize? [{READ|IRRESet},] (@ <ch\_list>)  
[SENSe:]COUNter:ABORt (@ <ch\_list>)  
[SENSe:]COUNter:DATA? (@ <ch\_list>)  
[SENSe:]COUNter:FREQUENCY[:DATA]? (@ <ch\_list>)  
[SENSe:]COUNter:FUNCTion {FREQUENCY|PERiod|DCYCLE|PWIDth|TOTalize}, (@ <ch\_list>)  
[SENSe:]COUNter:FUNCTion? (@ <ch\_list>)  
[SENSe:]COUNter:GATE:POLarity {NORMAl|INVerted}, (@ <ch\_list>)  
[SENSe:]COUNter:GATE:POLarity? (@ <ch\_list>)  
[SENSe:]COUNter:GATE:SOURce {INTernAl|EXTernAl}, (@ <ch\_list>)  
[SENSe:]COUNter:GATE:SOURce? (@ <ch\_list>)  
[SENSe:]COUNter:GATE:TIME[:INTernAl] {<time>|MIN|MAX|DEF}, (@ <ch\_list>)  
[SENSe:]COUNter:GATE:TIME[:INTernAl]? [{MIN|MAX},] (@ <ch\_list>)  
[SENSe:]COUNter:INITiate (@ <ch\_list>)

[SENSe:]COUNter:PERiod[:DATA]? (@<ch\_list>)

[SENSe:]COUNter:PWIDth[:DATA]? (@<ch\_list>)

[SENSe:]COUNter:SLOPe {NEGative|POSitive}, (@<ch\_list>)

[SENSe:]COUNter:SLOPe? (@<ch\_list>)

[SENSe:]COUNter:THReshold:VOLTage {<voltage>|MINIMAX|DEF}, (@<ch\_list>)

[SENSe:]COUNter:THReshold:VOLTage? [{MINIMAX},] (@<ch\_list>)

[SENSe:]COUNter:TOTalize:CLEar:IMMediate (@<ch\_list>)

[SENSe:]COUNter:TOTalize[:DATA]? (@<ch\_list>)

[SENSe:]COUNter:TOTalize:TYPE {READIRRESet}, (@<ch\_list>)

[SENSe:]COUNter:TOTalize:TYPE? (@<ch\_list>)

[SENSe:]MODule:COUNter:GATE:THReshold[:VOLTage] {<voltage>|MINIMAX|DEF}, {1|2|3|4|5|6|7|8}

[SENSe:]MODule:COUNter:GATE:THReshold[:VOLTage]? [{MINIMAX},] {1|2|3|4|5|6|7|8}

[SENSe:]TOTalize:CLEar:IMMediate (@<ch\_list>)

[SENSe:]TOTalize:DATA? (@<ch\_list>)

[SENSe:]TOTalize:SLOPe {NEGative|POSitive}, (@<ch\_list>)

[SENSe:]TOTalize:SLOPe? (@<ch\_list>)

[SENSe:]TOTalize:THReshold[:MODE] {ACITTL}, (@<ch\_list>)

[SENSe:]TOTalize:THReshold[:MODE]? (@<ch\_list>)

[SENSe:]TOTalize:THReshold:VOLTage {<voltage>|MINIMAX|DEF}, (@<ch\_list>)

[SENSe:]TOTalize:THReshold:VOLTage? [{MINIMAX},] (@<ch\_list>)

[SENSe:]TOTalize:TYPE {READIRRESet}, (@<ch\_list>)

[SENSe:]TOTalize:TYPE? (@<ch\_list>)

### External Clock Output Configuration

SOURce:MODule:CLOCK:FREQuency {<frequency>|MINIMAX|DEF}, {1|2|3|4|5|6|7|8}

SOURce:MODule:CLOCK:FREQuency? [{MINIMAX}, ] {1|2|3|4|5|6|7|8}

SOURce:MODule:CLOCK:LEVel {<voltage>|MINIMAX|DEF}, <slot>

SOURce:MODule:CLOCK:LEVel? [{MINIMAX}, ] <slot>

SOURce:MODule:CLOCK:STATe {OFF|0|1}, {1|2|3|4|5|6|7|8}

SOURce:MODule:CLOCK:STATe? {1|2|3|4|5|6|7|8}

## DAC Configuration Commands

OUTPut[:STATe] {OFF|O|ON|1}, (@<ch\_list>)  
OUTPut[:STATe]? (@<ch\_list>)

SOURce:CURRent[:LEVel] {<current>|MINIMAX|DEF}, (@<ch\_list>)  
SOURce:CURRent[:LEVel]? [{MINIMAX}, ] (@<ch\_list>)

SOURce:FUNcTion:TRIGger:SOURce {IMMediate|MANual|EXTernal}, (@<ch\_list>)  
SOURce:FUNcTion:TRIGger:SOURce? (@<ch\_list>)

SOURce:MODE {VOLTage|CURRent}, (@<ch\_list>)  
SOURce:MODE? (@<ch\_list>)

SOURce:MODule:CLOCK:FREQuency {<frequency>|MINIMAX|DEF}, {1|2|3|4|5|6|7|8}  
SOURce:MODule:CLOCK:FREQuency? [{MINIMAX}, ] {1|2|3|4|5|6|7|8}

SOURce:MODule:CLOCK:STATe {OFF|O|ON|1}, {1|2|3|4|5|6|7|8}  
SOURce:MODule:CLOCK:STATe? {1|2|3|4|5|6|7|8}

SOURce:MODule:TRIGger:EXTernal:IMMediate {1|2|3|4|5|6|7|8}

SOURce:MODule:TRIGger:OUTPut {OFF|O|ON|1}, {1|2|3|4|5|6|7|8}  
SOURce:MODule:TRIGger:OUTPut? {1|2|3|4|5|6|7|8}

SOURce:VOLTage[:LEVel] {<voltage>|MINIMAX|DEF}, (@<ch\_list>)  
SOURce:VOLTage[:LEVel]? [{MINIMAX}, ] (@<ch\_list>)

## Trace Waveform Configuration

SOURce:FUNcTion:CLOCK:EXTernal:DIVisor {<value>|MINIMAX|DEF}, (@<ch\_list>)  
SOURce:FUNcTion:CLOCK:EXTernal:DIVisor? [{MINIMAX}, ] (@<ch\_list>)

SOURce:FUNcTion:CLOCK:SOURce {INTernal|EXTernal|STEP}, (@<ch\_list>)  
SOURce:FUNcTion:CLOCK:SOURce? (@<ch\_list>)

SOURce:FUNcTion:CURRent:GAIN {<gain>|MINIMAX|DEF}, (@<ch\_list>)  
SOURce:FUNcTion:CURRent:GAIN? [{MINIMAX}, ] (@<ch\_list>)

SOURce:FUNcTion:CURRent:OFFSet {<offset>|MINIMAX|DEF}, (@<ch\_list>)  
SOURce:FUNcTion:CURRent:OFFSet? [{MINIMAX}, ] (@<ch\_list>)

SOURce:FUNcTion:ENABLE {OFF|O|ON|1}, (@<ch\_list>)  
SOURce:FUNcTion:ENABLE? (@<ch\_list>)

SOURce:FUNcTion:FREQuency {<frequency>|MINIMAX|DEF}, (@<ch\_list>)  
SOURce:FUNcTion:FREQuency? [{MINIMAX}, ] (@<ch\_list>)

SOURce:FUNcTion:HALT (@<ch\_list>)

SOURce:FUNcTion:SAMPle:PERiod {<period>|MINIMAX|DEF}, (@<ch\_list>)  
SOURce:FUNcTion:SAMPle:PERiod? [{MINIMAX}, ] (@<ch\_list>)

SOURce:FUNcTion:TRACe:NCYCles {<count>|MINIMAX|DEF|INFinity}, (@<ch\_list>)  
SOURce:FUNcTion:TRACe:NCYCles? [{MINIMAX}, ] (@<ch\_list>)

SOURce:FUNcTion:TRACe:SINdEx <point>, (@<ch\_list>)  
SOURce:FUNcTion:TRACe:SINdEx? (@<ch\_list>)

SOURce:FUNcTion:TRACe[:NAME] <name>, (@<ch\_list>)  
 SOURce:FUNcTion:TRACe[:NAME]? (@<ch\_list>)  
  
 SOURce:FUNcTion:TRIGger:IMMediate (@<ch\_list>)  
  
 SOURce:FUNcTion:VOLTagE:GAIN {<gain>|MINIMAXIDeF}, (@<ch\_list>)  
 SOURce:FUNcTion:VOLTagE:GAIN? [{MINIMAX}, ] (@<ch\_list>)  
  
 SOURce:FUNcTion:VOLTagE:OFFSet {<offset>|MINIMAXIDeF}, (@<ch\_list>)  
 SOURce:FUNcTion:VOLTagE:OFFSet? [{MINIMAX}, ] (@<ch\_list>)  
  
 TRACe:CATalog? {(@<channel>)|<slot>}  
  
 TRACe:DELeTe:ALL {(@<channel>)|<slot>}  
  
 TRACe:DELeTe[:NAME] {(@<channel>)|<slot>}, <name>  
  
 TRACe:FRee? {(@<channel>)|<slot>}  
  
 TRACe:POINts? {(@<channel>)|<slot>}, <name>  
  
 TRACe[:DATA] {1|2|3|4|5|6|7|8}, <name>, {<binary\_block>|<value>, <value> [,<value>, ... ]}  
 TRACe[:DATA]:DAC {1|2|3|4|5|6|7|8}, <name>, {<binary\_block>|<value>, <value> [,<value>, ... ]}  
  
 TRACe[:DATA]:FUNcTion {1|2|3|4|5|6|7|8}, <type>, <name>, <points>

## Monitor Commands

ROUTe:MONitor:DATA?  
  
 ROUTe:MONitor:MODE {CHANnelIDMM}  
 ROUTe:MONitor:MODE?  
  
 ROUTe:MONitor:STATe {OFFIOION1}  
 ROUTe:MONitor:STATe?  
  
 ROUTe:MONitor[:CHANnel] (@<channel>)  
 ROUTe:MONitor[:CHANnel]?  
  
 ROUTe:MONitor[:CHANnel]:ENABle {OFFIOION1}, (@<ch\_list>)  
 ROUTe:MONitor[:CHANnel]:ENABle? (@<ch\_list>)

## Scan Configuration Commands

ABORt

INITiate

FORMat:BORDer {NORMallSWAPped}

FORMat:BORDer?

FORMat:READIng:ALARm {OFFI0IONI1}

FORMat:READIng:ALARm?

FORMat:READIng:CHANnel {OFFI0IONI1}

FORMat:READIng:CHANnel?

FORMat:READIng:TIME {OFFI0IONI1}

FORMat:READIng:TIME?

FORMat:READIng:TIME:TYPE {ABSolutelRELative}

FORMat:READIng:TIME:TYPE?

FORMat:READIng:UNIT {OFFI0IONI1}

FORMat:READIng:UNIT?

READ? [(@<ch\_list>)]

ROUTE:CHANnel:ADVance:SOURce <source>

ROUTE:CHANnel:ADVance:SOURce?

ROUTE:CHANnel:DELay {<seconds>IMINIMAXIDEF}, (@<ch\_list>)

ROUTE:CHANnel:DELay? [{MINIMAX}, ] (@<ch\_list>)

ROUTE:CHANnel:DELay:AUTO {OFFI0IONI1}, (@<ch\_list>)

ROUTE:CHANnel:DELay:AUTO? (@<ch\_list>)

ROUTE:CHANnel:FWIRe <mode>, (@<ch\_list>)

ROUTE:CHANnel:FWIRe? (@<ch\_list>)

ROUTE:SCAN (@<scan\_list>)

ROUTE:SCAN?

ROUTE:SCAN:ADD (@<ch\_list>)

ROUTE:SCAN:REMOve (@<ch\_list>)

ROUTE:SCAN:ORDered {OFFI0IONI1}

ROUTE:SCAN:ORDered?

ROUTE:SCAN:SIZE?

SAMPlE:COUNT {<count>IMINIMAXIDEF}

SAMPlE:COUNT? [{MINIMAX}]

SWEep:COUNT {<count>IMINIMAXIDEF}

SWEep:COUNT? [{MINIMAX}]

TRIGger:COUNT {<count>IMINIMAXIDEF|INFinity}

TRIGger:COUNT? [{MINIMAX}]

TRIGger:SOURce {IMMediate|BUSIEXternal|ALARm1|ALARm2|ALARm3|ALARm4|TIMER}  
TRIGger:SOURce?

TRIGger:SOURce:ALARm[:MODE] {SINGLE|CONTInuous}  
TRIGger:SOURce:ALARm[:MODE]?

TRIGger:TIMER {<seconds>|MINIMAX|DEF}  
TRIGger:TIMER? [{MINIMAX}]

## Switch Control Commands

ROUTE:CHANnel:DRIVE:CLOSE:DEFault (@<ch\_list>)  
ROUTE:CHANnel:DRIVE:CLOSE:DEFault? (@<ch\_list>)

ROUTE:CHANnel:DRIVE:OPEN:DEFault (@<ch\_list>)  
ROUTE:CHANnel:DRIVE:OPEN:DEFault? (@<ch\_list>)

ROUTE:CHANnel:DRIVE:PAIRed[:MODE] {OFF|0|ON|1}, (@<ch\_list>)  
ROUTE:CHANnel:DRIVE:PAIRed[:MODE]? (@<ch\_list>)

ROUTE:CHANnel:DRIVE:PULSE[:MODE] {OFF|0|ON|1}, (@<ch\_list>)  
ROUTE:CHANnel:DRIVE:PULSE[:MODE]? (@<ch\_list>)

ROUTE:CHANnel:DRIVE:PULSE:WIDTH {<seconds>|MINIMAX|DEF}, (@<ch\_list>)  
ROUTE:CHANnel:DRIVE:PULSE:WIDTH? [{MINIMAX}, ] (@<ch\_list>)

ROUTE:CHANnel:DRIVE:STATE? (@<ch\_list>)

ROUTE:CHANnel:DRIVE:TIME:RECOvery {<seconds>|MINIMAX|DEF}, (@<ch\_list>)  
ROUTE:CHANnel:DRIVE:TIME:RECOvery? [{MINIMAX}, ] (@<ch\_list>)

ROUTE:CHANnel:DRIVE:TIME:SETTle {<seconds>|MINIMAX|DEF}, (@<ch\_list>)  
ROUTE:CHANnel:DRIVE:TIME:SETTle? [{MINIMAX}, ] (@<ch\_list>)

ROUTE:CHANnel:LABel:CLEar:MODule {1-8|SLOT1-SLOT8|ALL}

ROUTE:CHANnel:LABel[:DEFine] "<label>" , (@<ch\_list>)  
ROUTE:CHANnel:LABel[:DEFine]? [<type>,] (@<ch\_list>)

ROUTE:CHANnel:VERify[:ENABle] {OFF|0|ON|1}, (@<ch\_list>)  
ROUTE:CHANnel:VERify[:ENABle]? (@<ch\_list>)

ROUTE:CHANnel:VERify:POLarity {NORMAl|INVerted}, (@<ch\_list>)  
ROUTE:CHANnel:VERify:POLarity? (@<ch\_list>)

ROUTE:CHANnel:VERify:POSition:STATE? (@<ch\_list>)

ROUTE:CLOSE (@<ch\_list>)  
ROUTE:CLOSE? (@<ch\_list>)

ROUTE:CLOSE:EXCLusive (@<ch\_list>)

ROUTE:MODule:BUSY? {1-8|SLOT1-SLOT8|ANY}

ROUTE:MODule:WAIT {1-8|SLOT1-SLOT8|ANY}  
ROUTE:MODule:WAIT? {1-8|SLOT1-SLOT8|ANY}

ROUTe:OPEN (@<ch\_list>  
 ROUTe:OPEN? (@<ch\_list>  
  
 ROUTe:OPEN:ABUS [{<abus>|ALL}]  
  
 ROUTe:OPEN:ALL [{1-8|SLOT1-SLOT8|ALL}]  
  
 ROUTe:OPERation:OVERlap[:ENABLE] {OFF|ON|1}  
 ROUTe:OPERation:OVERlap[:ENABLE]?  
  
 ROUTe:RMODule:BANK:DRIVE[:MODE] {TTL|COLlector}, {1-4|BANK1-BANK4|ALL}, (@<rem\_ch\_list>  
 ROUTe:RMODule:BANK:DRIVE[:MODE]? {1-4|BANK1-BANK4}, (@<rem\_ch\_list>  
  
 ROUTe:RMODule:BANK:LED:DRIVE[:ENABLE] {OFF|ON|1}, {1-4|BANK1-BANK4|ALL}, (@<rem\_ch\_list>  
 ROUTe:RMODule:BANK:LED:DRIVE[:ENABLE]? {1-4|BANK1-BANK4}, (@<rem\_ch\_list>  
  
 ROUTe:RMODule:BANK:LED:DRIVE:LEVel {<amps>|MIN|MAX|DEF}, {1-4|BANK1-BANK4|ALL}, (@<rem\_ch\_list>  
 ROUTe:RMODule:BANK:LED:DRIVE:LEVel? {1-4|BANK1-BANK4}, (@<rem\_ch\_list>  
  
 ROUTe:RMODule:BANK:PRESet {1-4|BANK1-BANK4|ALL}, (@<rem\_ch\_list>  
  
 ROUTe:RMODule:DRIVE:LIMit {<max\_drives>|MIN|MAX|DEF}, (@<rem\_ch\_list>  
 ROUTe:RMODule:DRIVE:LIMit? [{MIN|MAX}, ] (@<rem\_ch\_list>  
  
 ROUTe:RMODule:DRIVE:SOURce:BOOT {OFF|INTernal|EXTernal}, (@<rem\_ch\_list>  
 ROUTe:RMODule:DRIVE:SOURce:BOOT? (@<rem\_ch\_list>  
  
 ROUTe:RMODule:DRIVE:SOURce[:IMMEDIATE] {OFF|INTernal|EXTernal}, (@<rem\_ch\_list>  
 ROUTe:RMODule:DRIVE:SOURce[:IMMEDIATE]? (@<rem\_ch\_list>  
  
 SYSTem:CDEscription? {1|2|3|4|5|6|7|8}  
  
 SYSTem:CDEscription:RMODule? (@<rem\_ch>) [, {DISTribution1-DISTribution4}]  
  
 SYSTem:CPON {1|2|3|4|5|6|7|8}  
  
 SYSTem:CTYPE? {1|2|3|4|5|6|7|8}  
  
 SYSTem:CTYPE:RMODule? (@<rem\_ch>) [, {DISTribution1-DISTribution4}]  
  
 SYSTem:MODule:PFAil:JUMPer:AMP5? {1|2|3|4|5|6|7|8} (34937A/938A only)  
  
 SYSTem:MODule:TEMPerature? [{TRANsducer|TTHReshold}], {1|2|3|4|5|6|7|8} (34937A/938A only)  
  
 SYSTem:MODule:WIRE:MODE {WIRE1|WIRE2}, {1|2|3|4|5|6|7|8} (34923A/925A/933A only)  
  
 SYSTem:RMODule:RESet {1|2|3|4|5|6|7|8}  
  
 SYSTem:RMODule:STATus? {1|2|3|4|5|6|7|8}



## Sequence Operation Commands

ROUTe:SEQuence:ABORt  
ROUTe:SEQuence:BUSY?  
ROUTe:SEQuence:CATalog?  
ROUTe:SEQuence:DEFine <name>, "<commands>"  
ROUTe:SEQuence:DEFine? <name>  
ROUTe:SEQuence:DELete:ALL  
ROUTe:SEQuence:DELete[:NAME] <name>  
ROUTe:SEQuence:RUNNing:NAME?  
ROUTe:SEQuence:TRIGger[:IMMediate] <name>  
ROUTe:SEQuence:TRIGger:SOURce <name>, {ALARm1|ALARm2|ALARm3|ALARm4|MANual}  
ROUTe:SEQuence:TRIGger:SOURce? <name>  
ROUTe:SEQuence:WAIT

## Triggering Commands

\*TRG  
INITiate  
READ? [(@<ch\_list>)]  
TRIGger:COUNT {<count>|MINIMAX|DEF|INFinity}  
TRIGger:COUNT? [{MINIMAX}]  
TRIGger:DELay {<seconds>|MINIMAX}  
TRIGger:DELay? [{MINIMAX}]  
TRIGger:DELay:AUTO {OFF|ON|1}  
TRIGger:DELay:AUTO?  
TRIGger:SOURce {IMMediate|BUSIEXTernal|TIMER}  
TRIGger:SOURce?  
TRIGger:TIMer {<seconds>|MINIMAX|DEF}  
TRIGger:TIMer? [{MINIMAX}]

## Alarm Limit Commands

CALCulate:LIMit:LOWer {<value>|MINIMAX|DEF}, (@<ch\_list>)  
CALCulate:LIMit:LOWer? [{MINIMAX},] (@<ch\_list>)

CALCulate:LIMit:LOWer:STATe {OFF|0|ON|1}, (@<ch\_list>)  
CALCulate:LIMit:LOWer:STATe? (@<ch\_list>)

CALCulate:LIMit:UPPer {<value>|MINIMAX|DEF}, (@<ch\_list>)  
CALCulate:LIMit:UPPer? [{MINIMAX},] (@<ch\_list>)

CALCulate:LIMit:UPPer:STATe {OFF|0|ON|1}, (@<ch\_list>)  
CALCulate:LIMit:UPPer:STATe? (@<ch\_list>)

OUTPut:ALARm{1|2|3|4}:CLEar

OUTPut:ALARm:CLEar:ALL

OUTPut:ALARm:MODE {LATCh|TRACK}  
OUTPut:ALARm:MODE?

OUTPut:ALARm{1|2|3|4}:SEQuence?

OUTPut:ALARm:SLOPe {NEGative|POSitive}  
OUTPut:ALARm:SLOPe?

OUTPut:ALARm{1|2|3|4}:SOURce (@<ch\_list>)  
OUTPut:ALARm{1|2|3|4}:SOURce?

SYSTem:ALARm?

## Measurement Statistics Commands

CALCulate:AVErAge:AVErAge? [(@<ch\_list>)]

CALCulate:AVErAge:CLEar [(@<ch\_list>)]

CALCulate:AVErAge:COUNt? [(@<ch\_list>)]

CALCulate:AVErAge:MAXimum? [(@<ch\_list>)]

CALCulate:AVErAge:MAXimum:TIME? [(@<ch\_list>)]

CALCulate:AVErAge:MINimum? [(@<ch\_list>)]

CALCulate:AVErAge:MINimum:TIME? [(@<ch\_list>)]

CALCulate:AVErAge:PTPeak? [(@<ch\_list>)]

DATA:LAST? [,(@<channel>)]

## Reading Memory Commands

DATA:POINts:EVENT:THReshold <num\_readings>

DATA:POINts:EVENT:THReshold?

DATA:POINts?

DATA:REMOve? <num\_readings>

FETCh?

R? [<max\_count>]

SYSTem:TIME:SCAN?

## Mx+B Scaling Commands

CALCulate:SCALe:GAIN <gain> [, (@<ch\_list>)]

CALCulate:SCALe:GAIN? (@<ch\_list>)

CALCulate:SCALe:OFFSet <offset> [, (@<ch\_list>)]

CALCulate:SCALe:OFFSet? (@<ch\_list>)

CALCulate:SCALe:STATe {OFF|O|ON|1} [, (@<ch\_list>)]

CALCulate:SCALe:STATe? [(@<ch\_list>)]

CALCulate:SCALe:UNIT "<units>" [, (@<ch\_list>)]

CALCulate:SCALe:UNIT? [(@<ch\_list>)]

## Calibration Commands

CALibration?

CALibration:ABORt

CALibration:BEgin[:VOLtagE] [<setup\_#>, ] (@<channel>)

CALibration:COUNt? [{1-8|SLOT1-SLOT8|MAINframe|DMM}]

CALibration:LFRequency {50|60|400}

CALibration:LFRequency?

CALibration:MODule? [{1-8|SLOT1-SLOT8|ALL}]

CALibration:POINt? <value>

CALibration:SECure:CODE <new\_code>

CALibration:SECure:STATe {OFF|O|ON|1}, <code>

CALibration:SECure:STATe?

CALibration:STRing "<string>" [{1-8|SLOT1-SLOT8|MAINframe|DMM}]

CALibration:STRing? [{1-8|SLOT1-SLOT8|MAINframe|DMM}]

CALibration:VALue <value>

CALibration:VALue?

## State Storage Commands

\*RCL {1|2|3|4|5}  
\*SAV {1|2|3|4|5}  
MEMory:NSTates?  
MEMory:STATe:CATalog?  
MEMory:STATe:DELeTe {1|2|3|4|5}  
MEMory:STATe:DELeTe:ALL  
MEMory:STATe:NAME {1|2|3|4|5} [,<name>]  
MEMory:STATe:NAME? {1|2|3|4|5}  
MEMory:STATe:RECall:AUTO {OFF|0|ON|1}  
MEMory:STATe:RECall:AUTO?  
MEMory:STATe:RECall:SELeCt {0|1|2|3|4|5}  
MEMory:STATe:RECall:SELeCt?  
MEMory:STATe:VALid? {1|2|3|4|5}

## IEEE-488 Commands

\*CLS  
\*ESE <enable\_value>  
\*ESE?  
\*ESR?  
\*IDN?  
\*OPC  
\*OPC?  
\*RCL {1|2|3|4|5}  
\*RST  
\*SAV {1|2|3|4|5}  
\*SRE <enable\_value>  
\*SRE?  
\*STB?  
\*TRG  
\*TST?  
\*WAI

## System-Related Commands

\*IDN?

\*RST

\*TST?

CALibration:LFRrequency {50|60|400}

CALibration:LFRrequency?

DISPlay[:STATe] {OFF|O|ON|1}

DISPlay[:STATe]?

DISPlay:TEXT "<string>"

DISPlay:TEXT?

DISPlay:TEXT:CLEAr

SYSTem:ABUS:INTerlock:SIMulate {OFF|O|ON|1}

SYSTem:ABUS:INTerlock:SIMulate?

SYSTem:BEEPer

SYSTem:BEEPer:STATe {OFF|O|ON|1}

SYSTem:BEEPer:STATe?

SYSTem:CDEscription? {1|2|3|4|5|6|7|8}

SYSTem:CDEscription:RMODule? (@<rem\_ch>) [{,}{DISTribution1-DISTribution4}]

SYSTem:CPON {1|2|3|4|5|6|7|8}

SYSTem:CTYPe? {1|2|3|4|5|6|7|8}

SYSTem:CTYPe:RMODule? (@<rem\_ch>) [{,}{DISTribution1-DISTribution4}]

SYSTem:DATE <yyyy>,<mm>,<dd>

SYSTem:DATE?

SYSTem:DELAy[:IMMediate] <time>

SYSTem:ERRor?

SYSTem:PRESet

SYSTem:SECurity:IMMediate

SYSTem:TIME <hh>,<mm>,<ss.sss>

SYSTem:TIME?

SYSTem:TIME:SCAN?

SYSTem:VERSion?

## Remote Interface Configuration Commands

SYSTem:COMMunicate:ENABle {OFF|O|ON|1}, {GPIB|USB|LAN|SOCKET|TELNet|VXI11|WEB}  
SYSTem:COMMunicate:ENABle? {GPIB|USB|LAN|SOCKET|TELNet|VXI11|WEB}

SYSTem:COMMunicate:GPIB:ADDRess <address>  
SYSTem:COMMunicate:GPIB:ADDRess?

SYSTem:LOCK:OWNer?

SYSTem:LOCK:RELease

SYSTem:LOCK:REQuest?

## LAN Configuration Commands

SYSTem:COMMunicate:LAN:AUTOip {OFF|O|ON|1}  
SYSTem:COMMunicate:LAN:AUTOip?

SYSTem:COMMunicate:LAN:BSTatus?

SYSTem:COMMunicate:LAN:CONTRol?

SYSTem:COMMunicate:LAN:DHCP {OFF|O|ON|1}  
SYSTem:COMMunicate:LAN:DHCP?

SYSTem:COMMunicate:LAN:DNS <address>  
SYSTem:COMMunicate:LAN:DNS?

SYSTem:COMMunicate:LAN:DOMain "<name>"  
SYSTem:COMMunicate:LAN:DOMain? [{CURRENT|STATIC}]

SYSTem:COMMunicate:LAN:GATEway <address>  
SYSTem:COMMunicate:LAN:GATEway? [{CURRENT|STATIC}]

SYSTem:COMMunicate:LAN:HISTory:CLEar

SYSTem:COMMunicate:LAN:HISTory?

SYSTem:COMMunicate:LAN:HOSTname "<name>"  
SYSTem:COMMunicate:LAN:HOSTname? [{CURRENT|STATIC}]

SYSTem:COMMunicate:LAN:IPADdress <address>  
SYSTem:COMMunicate:LAN:IPADdress? [{CURRENT|STATIC}]

SYSTem:COMMunicate:LAN:KEEPlive {<seconds>|MINIMAX}  
SYSTem:COMMunicate:LAN:KEEPlive? [{MINIMAX}]

SYSTem:COMMunicate:LAN:MAC?

SYSTem:COMMunicate:LAN:SMASK <mask>  
SYSTem:COMMunicate:LAN:SMASK? [{CURRENT|STATIC}]

SYSTem:COMMunicate:LAN:TELNet:PROMpt "<string>"  
SYSTem:COMMunicate:LAN:TELNet:PROMpt?

SYSTem:COMMunicate:LAN:TELNet:WMESsage "<string>"  
SYSTem:COMMunicate:LAN:TELNet:WMESsage?

## Status System Commands

\*CLS

\*ESE <enable\_value>

\*ESE?

\*ESR?

\*SRE <enable\_value>

\*SRE?

\*STB?

STATus:ALARm:CONDition?

STATus:ALARm:ENABle <enable\_value>

STATus:ALARm:ENABle?

STATus:ALARm[:EVENT]?

STATus:MODule:ENABle <enable\_value>

STATus:MODule:ENABle?

STATus:MODule:EVENT?

STATus:MODule:SLOT[n]:CONDition?

STATus:MODule:SLOT[n]:ENABle <enable\_value>

STATus:MODule:SLOT[n]:ENABle?

STATus:MODule:SLOT[n][:EVENT]?

STATus:OPERation:CONDition?

STATus:OPERation:ENABle <enable\_value>

STATus:OPERation:ENABle?

STATus:OPERation[:EVENT]?

STATus:PRESet

STATus:QUEStionable:CONDition?

STATus:QUEStionable:ENABle <enable\_value>

STATus:QUEStionable:ENABle?

STATus:QUEStionable[:EVENT]?

SYSTem:ALARm?

SYSTem:MODule?

## Service-Related Commands

DIAGnostic:DMM:CYCLes? {1|2|3|4|5|6}

DIAGnostic:RELAy:CYCLes? (@<*ch\_list*>)

DIAGnostic:RELAy:CYCLes:CLEar (@<*ch\_list*>)

INSTrument:DMM:CONNect

INSTrument:DMM:CONNect?

INSTrument:DMM:DISConnect

INSTrument:DMM:DISConnect?

INSTrument:DMM:INSTalled?

INSTrument:DMM[:STATe] {OFF|0|ON|1}

INSTrument:DMM[:STATe]?