



Agilent 84811A Peak Power Sensor

Data Sheet

Frequency Range:

100 MHz to 18 GHz

Power Range:

0 to +20 dBm (1 mW to 100 mW)

SWR:

100 MHz to 12 GHz <1.5 12 GHz to 18 GHz <2.0

Maximum Peak Power:

+24 dBm (250 mW) for 5 minutes

Connector Type:

Type-N, male

Calibration Accuracy:

10 to 40 °C, ± 0.7 dB 0.1 to 12 GHz, ± 1.0 dB to 18 GHz. 0 to 10 °C and 40 to 55 °C: add ± 0.2 dB



Agilent Technologies