

PIO-96J-26636Board Configuration

Keithley Instruments, Inc. 28775 Aurora Road Cleveland, Ohio 44139 (440) 248-0400

Fax: (440) 248-6168 www.keithley.com

Description

This document contains information on the PIO-96J-26636 Parallel Digital I/O Board. The PIO-96J-26636 is the standard PIO-96J with RN1-12 populated with $10k\Omega$ resistor networks (Keithley p/n 09698).

The onboard $10k\Omega$ pull-up resistors are connected between each channel and the +5V. This prevents a floating input when a contact is open and gives CMOS compatibility for TTL signals. Replacement resistors, p/n 09698, can be ordered from Keithley. Figure 1 shows how this resistor makes an input of a PIO-96J-26636 board an effective circuit for monitoring contact closure. See Figure 1 for resistor connections. Refer to the PIO-96J User's manual for all other information concerning the PIO-96J-26636.

Figure 1
Contact-closure monitoring at an input of a
PIO-96J-26636 board

