
METREL MD 105 Non Contact Voltage Detector







☑ Easy to use,

Ideal tool for every electrician



The MD 105 is a basic non-contact voltage tester that features a visual display indicator and comes complete with a pocket clip.

The contact-less MD 105 voltage tester can, for example, detect live wires in splices, cable drums, socket outlets and switches. A defective lamp in a chain of lights can be localized within seconds. An invisible cable breakage in an extension lead is indicated to within a tolerance of just a few millimeters.

The Metrel MD 105 uses a capacitive measuring process. In contrast to inductive measurements, no flow of current is required.

TECHNICAL SPECIFICATIONS

| Function | Range |
|----------------------------|-------------------------------|
| Display | Visual |
| Measurement range | 110 1000 V AC |
| Integrated LED flash light | No |
| Power supply | 2 x 1,5 V batteries, type AAA |
| Overvoltage category | CAT III / 1000 V |
| Degree of protection | IP 44 |
| Dimensions | 142 x 26 mm |
| Weight | 22 g |

MEASURING FUNCTIONS:

• Non contact voltage detection from 110 V AC;

APPLICATION:

- · General purpose;
- · Low level electrical testing;
- Hobby work.

KEY FEATURES:

- 110 V ... 1000 V AC measurement
- CAT III / 1000 V overvoltage protection.

ORDERING INFORMATION:

Part No. MD 105



- Non Contact Voltage Detector MD 105
- 1,5 V battery test, type AAA, 2 pcs Instruction manual

