# **Panasonic**<sup>®</sup>

**DIGITAL PIANO** 

sx-NP10

Before connecting, operating or adjusting this product, please read these instructions completely. Please keep this manual for future reference.

## OWNER'S MANUAL

#### WARNING:

TO REDUCE THE RISK OF FIRE, ELECTRIC SHOCK OR PRODUCT DAMAGE, DO NOT EXPOSE THIS APPARATUS TO RAIN, MOISTURE, DRIPPING OR SPLASHING AND THAT NO OBJECTS FILLED WITH LIQUIDS, SUCH AS VASES, SHALL BE PLACED ON THE APPARATUS

(for U.S.A. and Canada)

#### **CAUTION:**

TO PREVENT ELECTRIC SHOCK MATCH WIDE BLADE OF PLUG TO WIDE SLOT, FULLY INSERT

#### VAROITUS:

TULIPALO-, SAHKOISKUVAARAN TAI TUOTETTA KOHTAAVAN MUUN VAHINGON VAHENTAMISEKSI ΕI LAITETTA SAA ALTISTAA SATEELLE. KOSTEUDELLE, VESIPISAROILLE TAI ROISKEELLE. EIKA **NESTETTA** SISALTAVIA ESINEITA. KUTEN ESIMERKIKSI MALJAKOITA. ASETTAA LAITTEEN PAALLE

#### ADVARSEL:

FOR Å REDUSERE FAREN FOR BRANN, ELEKTRISK STØT ELLER SKADER PÅ PRODUKTET, MÅ DETTE APPARATET IKKE UTSETTES FOR REGN, FUKTIGHET, VANNDRÅPER ELLER VANNSPRUT. DET MÅ HELLER IKKE PLASSERES GJENSTANDER FYLT MED VANN, SLIK SØM BLOMSTERVASER, OPPÅ APPARATET

THE FOLLOWING APPLIES ONLY
IN THE U.S.A. AND CANADA



#### CAUTION

RISK OF ELECTRIC SHOCK DO NOT OPEN



CAUTION

TO REDUCE THE RISK OF ELECTRIC SHOCK, DO NOT REMOVE SCREWS NO USER-SERVICEABLE PARTS INSIDE

REFER SERVICING TO QUALIFIED SERVICE PERSONNEL



The lightning flash with arrowhead symbol, within an equilateral triangle, is intended to alert the user to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons



The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the appliance

#### **VARNING:**

FOR ATT MINSKA RISKEN FOR ELDSVÅDA, ELEKTRISKA STOTAR OCH SKADOR PÅ PRODUKTEN FÅR DEN INTE UTSATTAS FOR REGN, FUKTIGHET, VATTENDROPPAR ELLER VATTENSTANK, OCH INGA FOREMÅL SOM AR FYLLDA MED VATSKA, SÅ SOM VASER, BOR PLACERAS PÅ APPARATEN

THIS UNIT IS INTENDED FOR USE IN TROPICAL CLIMATES
DENNA ENHET AR AVSEDD FOR ANVANDNING PÅ PLATSER MED TROPISKT KLIMAT
TAMA LAITE ON TARKOITETTU KAYTETTAVAKSI TROOPPISESSA ILMASTOSSA
DETTE APPARATET ER BEREGNET TIL BRUK UNDER TROPISKE KLIMAFORHOLD

#### Caution for AC Main Lead

# (For United Kingdim) (For the type as shown in figures A and B)

For your safety, please read the following text carefully

This appliance is supplied with a moulded three pin mains plug for your safety and convenience. A 5-ampere fuse is littled in this plug. Should the fuse need to be replaced please ensure that the replacement fuse has a rating of 5-ampere and that it is approved by ASTA or BSI to BS1362. Check for the ASTA mark or the BSI mark on the body of the fuse.

If the plug contains a removable fuse cover you must ensure that it is refitted when the fuse is replaced If you lose the fuse cover the plug must not be used until a replacement cover is obtained

A replacement fuse cover can be purchased from your local dealer

#### **CAUTION!**

IF THE FITTED MOULDED PLUG IS UNSUITABLE FOR THE SOCKET OUTLET IN YOUR HOME THEN THE FUSE SHOULD BE RE-MOVED AND THE PLUG CUT OFF AND DIS-POSED OF SAFELY THERE IS A DANGER OF SEVERE ELECTRICAL SHOCK IF THE CUT OFF PLUG IS INSERTED INTO ANY 13-AMPERE SOCKET

If a new plug is to be fitted please observe the wiring code as stated below. If in any doubt please consult a qualified electrician

#### **IMPORTANT**

The wires in this mains lead are coloured in accordance with the following code

Blue Neutral, Brown Live

As these colours may not correspond with the coloured markings identifying the terminals in your plug, proceed as follows

The wire which is coloured Blue must be connected to the terminal which is marked with the letter N or coloured Black or Blue

The wire which is coloured Brown must be connected to the terminal which is marked with the letter L or coloured Brown or Red

WARNING DO NOT CONNECT EITHER WIRE TO THE EARTH TERMINAL WHICH IS MARKED WITH THE LETTER E, BY THE EARTH SYMBOL ± OR COLOURED GREEN OR GREEN/ YELLOW

## THIS PLUG IS NOT WATERPROOF -KEEP DRY


#### Before use

Remove the connector cover


#### How to replace the fuse

The location of the fuse differ according to the type of AC mains plug (figures A and B). Confirm the AC mains plug fitted and follow the instructions below illustrations may differ from actual AC mains plug.

#### 1 Open the fuse cover with a screwdriver



## 2 Replace the fuse and close or attach the fuse cover



## IMPORTANT SAFETY NOTICE

#### RADIO FREQUENCY INTERFERENCE STATEMENT

Class B Digital Device/Info mation Technology Equipment

#### Note:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures.

- Recrient or relocate the receiving antenna
- Increase the separation between the equipment and receiver
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected
- Consult the dealer or an experienced radio/TV technician for help.

#### FCC Warning

To assure continued FCC emission limit compliance, use only the provided AC Adaptor, the proper power supply cord and the shielded interface cable when connecting this device to the computer Also, any unauthorized changes or modifications to this equipment would void the user's authority to operate this device

This device complies with Part 15 of the FCC Rules Operation is subject to the following two conditions

- (1)This device may not cause harmful interference, and
- (2)this device must accept any interference received, including interference that may cause undesired operation

Responsible Party Matsushita Electric Corporation of America

One Panasonic Way Secaucus, NJ, 07094 USA Telephone No 1-800-211-7262

The model number and serial number are found underneath the keyboard Please note the model and serial numbers in the space provided below and retain this sheet as a permanent record of your purchase to aid identification in the event of theft

MODEL NUMBER

SERIAL NUMBER

## **Cautions for safest use of this unit**

#### Installation location

- 1 A well-ventilated place
  - Take care not to use this unit in a place where it will not receive sufficient ventilation, and not to permit the ventilation holes to be covered by curtains, or any similar materials
- 2 Place away from direct sunlight and excessive heat from healing equipment
- 3 A place where humidity, vibration and dust are minimized

#### Power source

- 1 Be sure the line voltage selector is in accordance with local voltage in your area before connecting the plug to the socket
- 2 DC power cannot be used

#### Handling the power cord

- Never louch the power cord, or its plug, with wet hands
- 2 Don't pull the power cord

## Metal items inside the unit may result in electric shock or damage.

Do not permit metal articles to get inside the unit

Be especially careful with regard to this point if children are near this unit. They should be warned never to try to put anything inside

If, nevertheless, some such article does get inside, disconnect the power cord plug from the electrical outlet, and contact the store where the unit was purchased

#### If water gets into the unit

Disconnect the power cord plug from the electrical outlet, and contact the store where it was purchased

As a precaution, it is suggested that flower vases and other containers which hold liquids not be placed on the top of this unit

#### This product may receive radio interference caused by mobile telephones during use. If such interference is apparent, please increase separation between the product and the mobile telephone.

#### If operation seems abnormal

Immediately turn off the power, disconnect the power cord plug from the electrical outlet, and contact the store where it was purchased

Discontinue using the unit at once Failure to do so may result in additional damage or some other unexpected damage or accident

 Because the power source is located inside the unit, it is normal for the cabinet to become warm

#### A word about the power cord

If the power cord is scarred, is partially cut or broken, or has a bad contact, it may cause a fire or serious electrical shock if used NEVER use a damaged power cord for any appliance Moreover, the power cord should never be forcibly bent

## Don't touch the inside parts of this unit.

Some places inside this unit have high voltage potential. Never try to remove the top or back panels of this unit, or to touch inside parts by hand or with tools.

Contact someone who is qualified in order to inspect the inside, or to replace a fuse, if such becomes necessary. Never attempt to do these things yourself

#### Maintenance

The following suggestions will assist you in keeping the unit in top condition

- Be sure to switch the instrument off after use, and do not switch the unit on and off in quick succession, as this places an undue load on the electronic components
- To keep the luster of the surface and buttons, simply use a clean, damp cloth, polish with a soft, dry cloth Polish may be used but do not use thinners or petrochemical-based polishes
- A wax-based polish may be used on the cabinet, although you will find that rubbing with a soft cloth will suffice
- SVENSK Det kan intraffa att den har produkten under anvandningen tar emot radiostorningar, orsakade av mobiltelefoner Oka avständet mellan produkten och mobiltelefonen om storningarna ar uppenbara

# SERVICE MUST BE CARRIED OUT BY DEALER OR OTHER QUALIFIED PERSON

## IMPORTANT SAFETY INSTRUCTIONS

Read these operating instructions carefully before using the unit. Follow the safety instructions on the unit and the safety precautions listed below. Keep these operating instructions handy for future reference.

#### Safety

- Power Source—Connect the unit to a power source of the type described in these instructions or as marked on the unit
- 2 Polarization—The unit is equipped with a polarized power plug where one blade is wider than the other This safety feature ensures that the plug fits into your household AC outlet only one way. If the plug doesn't fit one way, try reversing it. If the plug still doesn't fit, contact an electrician to replace the obsolete outlet. Do not attempt to defeat the safety purpose of the plug.
- 3 Power Cord protection—Route the AC power supply cord so that it will not be walked on or pinched by items placed on or against it. Never take hold of the plug or cord with wet hands. Always grasp the plug body firmly when connecting and disconnecting it.
- 4. Overloading—When connecting the AC power supply cord, be careful not to overload the household AC outlet, extension cord, or outlet from any other device as this can result in fire or electric shock
- 5 Nonuse periods—Turn the unit off when it is not in use. Unplug the unit from the household AC outlet if it is not to be used for a long time. Unplug the unit during lightning storms.
- Attachments and accessories—Use only the attachments and accessories recommended in these operating instructions

#### Installation

#### Placement

- Ventilation—Situate the unit so that it receives proper ventilation. Do not install in a confined space such as a bookcase or cabinet. Allow at least 10 cm (4 inches) clearance from the rear of the unit. To prevent the risk of electric shock or fire due to overheating ensure curtains and other materials do not obstruct the unit's ventilation.
- 2 Foreign material—Ensure objects and liquids do not get into the unit. Avoid exposing the unit to excessive smoke, dust, mechanical vibration, and shock
- Magnetism—Situate the unit away from equipment and devices that generate strong magnetic fields
- 4 Stacking—Do not place heavy objects on top of this unit
- 5 Surface-Place the unit on a flat, level surface

6 Carls and stands—Use the unit only with carls and stands recommended by the manufacturer Move carts with care Sudden stops, excessive force, and uneven surfaces can cause carts to overturn



 Wall and ceiling mounting—Do not mount the unit on walls or ceilings unless specified in the instructions

#### Environmnet

- Water and moisture—Do not use the unit near water, such as near a bathtub or swimming pool. Avoid damp basements
- 2 Heal—Situate the unit away from heat sources, such as radiators
  - Do not situate where temperatures fall below 5°C (41°F) or rise above 35°C (95°F)

#### Maintenance

(See page 5 for details )

Unplug the unit from the household AC outlet before cleaning

Clean with a damp cloth

Do not use abrasive pads, scouring powders, or solvents


#### **Service**

- Damage Requiring Service—The unit should be serviced by qualified service personnel if
  - (a) The AC power supply cord or the plug has been damaged, or
  - (b) Objects or liquids have gotten into the unit, or
  - (c) The unit has been exposed to rain, or
  - (d) The unit does not operate normally or exhibits a marked change in performance, or
  - (e) The unit has been dropped or the cabinet damaged
- Servicing—Do not attempt to service the unit beyond that described in these operating instructions. Refer all other servicing to authorized servicing personnel.
- 3 Replacement parts—When parts need replacing ensure the servicer uses parts specified by the manufacturer or parts that have the same characteristics as the original parts. Unauthorized substitutes may result in fire, electric shock, or other hazards.
- Safety check—After repairs or service, ask the servicer to perform safety checks to confirm that the unit is in proper working condition


### **Getting started**

### Before you play


- 1 Plug the power cord into an outlet
- 2 Set up the music stand (included)
- To set up the music stand, insert the transparent board in the groove and position it so that it is easy to read the music score



3 Push the middle of keyboard section back until it clicks into place



4 With your hand beneath the middle of the keyboard section, slowly pull it towards you until it clicks into place



- After pulling, gently push the middle of the keyboard section away from you to confirm that it is locked into place
- When stowing the keyboard section, pull it slightly towards you until a click is heard, and then slowly push it back (away from you) until a click is heard


#### CAUTION

- Take care not to pinch your fingers when opening and closing the keyboard section
- Do not hold the upper side of the keyboard section when opening or closing it. To avoid pinching your fingers, be sure to hold only the underside.




- To avoid pinching your lingers, do not touch the rails to the left and right of the keyboard section
- Do not sit on or hang from the keyboard section, as doing so may cause it to fall over
- Do not place heavy objects on the keyboard section. Also, opening or closing the keyboard section with force may cause anything placed on the instrument to fall, open and close it gently.

#### 5 Turn on the POWER switch




- The indicator lamp lights up when power is on
- You can now play the keyboard for a plane performance
- 6 Adjust the loudness with the MAIN VOLUME control



 A commercially sold microphone can be connected to the MIC terminal (refer to page 10). Adjust the volume with the MIC VOLUME control.


### Listen to the demonstration.

⇒While pressing the MODE SET button (to the left of keyboard), press one of the keyboard keys that corresponds to an indicated DEMO number



- The list of demo songs is on page 14
- MEDLEY A medley of all the tunes
- To discontinue the demonstration while it is playing, press the MODE SET button
- The MEDLEY will repeat continuously until the MODE SET button is pressed
- The indicator for the MODE SET button flashes during the demonstration performance

Operation



#### A. Change the sound


- ⇒While pressing the SOUND button, press one of the keyboard keys that corresponds to an indicated SOUND name
- Alternatively, each time you press the SOUND button, the sound changes to the one indicated to the right of the sound that is currently active (If PIPE ORGAN is the currently active sound, the sound will change to GRAND PIANO)
- In the initialized state (the settings in effect when the instrument is turned on), the GRAND PIANO sound is selected

#### ■ Mix two sounds

- ⇒To mix two different sounds, while pressing the SOUND builton, press the two keys for the desired sounds
- . Both sounds are produced when you play a key

#### B. Add reverb

- ⇒While pressing the MODE SET button, press the keyboard key that corresponds to REVERB OFF or ON
- When the MODE SET button is pressed, its indicator flashes
- In the initialized state, the setting is ON, and reverb is added to the sound



#### Sustain pedal

The sound fades gradually after the keys are released

#### Sostenuto pedal

If the pedal is pressed while the keys are pressed, a sustain effect is applied to those notes only


#### Soft pedal

The tones are softened, and the volume is slightly

## **Mode Setting**

While the MODE SET button is depressed, the keys indicated in the illustration below are used for setting the functions

- ⇒ Keep the MODE SET button depressed while following the procedures below
- When the MODE SET button is released, the function-setting mode is canceled, and the keys return to the performance mode



- If the left pedal is depressed during function-setting, even if you release the MODE SET button, the function-setting mode remains active
- During function-setting, the indicator for the MODE SET button is lit. When you press a key to select a setting, the indicator flashes and a confirming beep is heard.
- All settings revert to their factory-preset settings when the power is turned off

#### Tuning (adjust the pitch)

You can adjust the pitch of this instrument when you are playing together with other instruments

- ⇒ Press F#6 to set the pitch to 440 Hz (initial setting)
- ⇒ Press G#6 to set the pitch to 442 Hz
- ⇒ Press A#6 to set the pilch to 443 Hz

#### ■ Fine tuning

- ⇒ Each time G6 is pressed, the pitch is raised by 0.8
- ⇒ Each time F6 is pressed, the pitch is lowered by 0 B cent
- If you altempt to raise the pitch above 452.7 Hz or lower it below 427.5 Hz, the confirming beep does not sound even when the key is pressed
- You can hold the G6 or F6 key down to change the pitch quickly. In this case, the MODE SET indicator changes from flashing to lit when the highest or lowest pitch is reached.

#### Basic channel

Assign the MIDI basic channel


- ⇒Press the key corresponding to the basic channel number (Refer to the illustration above)
- The default setting is channel 1
- When using the included "NP10 On Stage" software set the channel number to 1

#### Local control

This setting is for when this instrument is used as the master keyboard

- ⇒The local control is switched between on (default) and off each time the D#6 key is pressed
- When the local control is set to off, the signals generated by the keys and pedals of this instrument are not sent to its sound generator, but are handled only as MIDI output (this instrument generates no sound)

### **Connections**



#### MIC

A commercially sold microphone can be connected to this terminal

Adjust the volume with the MIC VOLUME control


#### **AUX IN**

The terminal to input signals from the LINE OUT terminal of other equipment (RCA pin plug)

#### USB

The terminal to connect a personal computer to this instrument with a USB cable (Type AB, sold commercially). After installing the application software "NP10 On Stage" from the included CD-ROM in your computer, you can control this instrument with your computer, record your performance in your computer, thus enhancing your enjoyment of this instrument.

(For information about installing the application, please refer to the separate Device Driver Installation manual provided)



(Beneath the main unit, on the left side)

#### PHONES x2

You can connect up to two sets of headphones (sold separately) (When headphones are connected, the instrument's speakers are disabled)

#### LINE OUT

The terminal to connect an external speaker system or the like, for outputting sound from this instrument (RCA pin plug)

 To output monaural sound, use the R/MONO terminal (in this case, do not connect anything to the L terminal)

#### MIDI IN

The terminal to receive MIDI data from other equipment

#### MIDI OUT

The terminal to send MIDI data to other equipment

Use a commercially sold MIDI cable to connect MIDI equipment


## Symptoms which appear to be signs of trouble

Phenomenon	Remedy
No sound is produced when the	<ul> <li>No sound is produced if the MAIN VOLUME is set to MIN. Use the sliding</li> </ul>
keyboard is	control to set the volume to an appropriate level
	If the MIDI LOCAL CONTROL is set to off, set it to on (refer to page 9)


## **Assembly**

Follow the steps below to assemble your Technics plano. Make sure you are using the correct parts and that they are in the correct direction.


- At least 2 people are required for assembly
- To disassemble the piano, reverse the procedure
- 1 Remove the packing and take the parts out of the carton Confirm that all the parts on the printed list are present



2 Affix the right and left side planks to the pedal box



- (1) Use the 4 brass-colored screws to secure the planks
- (2) Loosen the pedal cord, stowed on the inner side of the pedal box, and extend it



time)
4 Place the piano body on the stand

#### WARNING


Avoid pinching your fingers

#### Note 1

Holding the piano body at least 10 cm in from the edge, place it on the stand so that it does not fall off

#### Note 2


If the piano body is placed too far to the right or left, or to the front or back, it will become unstable




Turn each of the 4 black screws 5 or 6

times (do not screw in lightly at this

5 Secure the plano body to the stand



- (1) Insert 2 black screws in the 2 rear screw holes on the underside of the piano body, and turn each screw 5 or 6 times. Push the piano body forward so that the screws are fully inserted in the cutout of the metal piece on either side plank (This enables you to easily position the piano body on the stand.)
- (2) Adjust the piano body so that it evenly aligns with the stand
- (3) Positioning the piano body on the stand, confirm that the 4 black screws can easily be inserted
- (4) Tighten the 4 screws securely
- (5) Securely tighten the 4 black screws that affix the cross bar
- 6 Connect the pedal cord and power cord to the terminals




- (1) Plug the pedal cord and power cord into the terminals on the rear of the plano
- (2) Remove the backing from the clamps and affix them as shown in the figure. Secure the pedal cord to the clamps.

## Confirm: After assembling, check these points

- Are any parts left over?
  - → Check the assembly procedure again.
- Does the plano rattle when it is rocked?
  - → Make sure all the screws are securely tightened
- Is the power cord firmly inserted?
  - → Check again
- Is the plug of the pedal cord inserted as far into the connector terminal as it will go?
  - If it is not completely inserted, the sustain and other pedal functions may not work
- When the piano has been moved or transported, retighten the screws securely

#### ■ After setting up

After assembling the instrument and positioning it in its intended place of use, remove the 3 gold screws and 3 spacers that secure the sliding keyboard



#### Note


Please keep the securing screws and spacers in a safe place for use in the event of a future move

#### ■ Caution when transporting this instrument

When transporting this instrument (during a move, for example), affix the special securing parts to the keyboard section.


At this time, do not completely stow the keyboard section inside the main unit, but allow it to protrude about 2 cm towards the front, affixing it by following the procedure below

- (1) Place each of the three spacers so that they will be positioned in the gap between the screw and the panel
- (2) Partly screw in the 3 securing screws, making sure that each of the spacers is lightly held in place
- (3) Securely tighten each screw



#### ■ Caution

Please do not sit on or hang from the keyboard section (If a strong force is applied, there is a danger of its falling)



When removing the securing screws, first affix the plano body to the stand and perform it

## **MIDI Implementation Chart**

Digital piano [ SX-NP10 ]

Function		Transmilled	Recognized	Remarks	
Basic Channel	Default Changed	 1–16	1 1–16		
Mode	Default Messages Altered	3 × —	3 × —		
Note Number	True vaice	21-108 —	0-127 0-127*		
Velocity	Note ON Note OFF	○ x(9nh v=0)	O K		
After Touch	Key's Ch's	×	x x		
Pitch Bend		ж	×		
Control Change Prog Change	64 66 67 74 True #	0 0 x	O O O 1–128	sustain pedal sostenuto pedal soft pedal brilliance  B built-in sounds arranged in GM map	
			0		
System Exc System Common	Song Pos Song Sel Tune	x x x	x x x		
System Real Time	Clock Commands	x x	×	start/slop, continue	
Aux Messages	Local ON/OFF All Noles OFF Active Sense Resel	ж × О ×	0 0 0 ×		
Notes Depends on the TRANSPOSE selling					

Mode 1 Mode 3 OMNI ON, POLY OMNI OFF, POLY Mode 2 Mode 4 OMNI ON, MONO OMNI OFF, MONO Yes Nο

## **Specifications**

	SX-NP10	
KEYBOARD	88 KEYS (WITH TOUCH RESPONSE)	
SOUND GENERATOR	PCM	
MAX POLYPHONY	32 NOTES	
SOUND	8 SOUNDS GRAND PIANO, UPRIGHT PIANO, E PIANO 1, E PIANO 2, HARPSI, VIBES, STRINGS, PIPE ORGAN	
PEDALS	SUSTAIN, SOFT, SOSTENUTO	
FUNCTIONS	MAIN VOLUME, MIC VOLUME, DEMO, TUNING, REVERB, BASIC CHANNEL, LOCAL CONTROL	
TERMINALS	PHONES ≥ 2, MIDI (IN, OUT), AUX IN (R, L), LINE OUT (R/MONO, L), MIC, USB	
OUTPUT	80 W (40 W × 2)	
SPEAKERS	14 cm × 2	
POWER REQUIREMENT	85 W/110 W (NORTH AMERICA AND MEXICO)	
	AC 120/220/240 V 50/60 Hz AC 120V 60 Hz (NORTH AMERICA AND MEXICO) AC 230-240V 50/60 Hz (EUROPE, AUSTRALIA, NEW ZEALAND, SINGAPORE AND PHILIPPINES)	
DIMENSIONS (WxHxD)*	142 3 cm × 98 7 cm × 55 9 cm (56-1/32" × 38-27/32" × 22") D 45 1 cm (17-3/4") when the keyboard section is closed	
NET WEIGHT	58 kg (127 9 lbs )	
ACCESSORIES	MUSIC STAND, AC CORD, CD ROM	

<sup>\*</sup> Including the music stand

#### **DEMO Songs**

No	TITLE	COMPOSER
1	Amazing Grace	traditional
2	Arabeske Op 18	Schumann
3	Beautiful Oreamer	Foster
4	Panasonic Original	
5	Swannee River	traditional
6	Danny Boy	traditional

Design and specifications are subject to change without notice

■ Supplied accessory
Please check the supplied accessory
AC cord
Music Stand
™ CD-ROM
NOTE
The included AC cord is for use with this unit only
Do not use it with other equipment

	_			
		<u> </u>		
-	<del>-</del>			
	_			
	_		<del></del>	
DIVISION OF MATSU	MER ELECTRONICS COMPAN SHITA ELECTRIC CORPORA Caucus New Jersey 07094	NY FION OF AMERICA		Printed in Japan
Consumerproducts @ Panasonic com				

Se06015tj

ENGLISH