

SYSTEM CONTROL & SERVO ICs DC VOLTAGE CHART (SP MODE)

Ref. No.	IC1501					IC1502					IC2001											
MODE	1	2	3	4		1	2	3		1	2	3	4	5	6							
STOP	1.2	2.4	5.0	0.0		0.0	1.3	5.0		6.1	0.0	4.9	1.2	0.0	5.0							
PLAY	1.2	2.4	5.0	0.0		0.0	1.3	5.0		6.1	0.0	4.9	1.2	0.0	5.0							
REC	1.2	2.4	2.5	0.0		0.0	1.3	4.9		6.0	0.0	4.9	1.2	0.0	5.0							
F.F	1.2	2.4	2.6	0.0		0.0	1.3	2.5		6.5	0.0	4.9	1.2	0.0	5.0							
REW	1.2	2.4	2.5	0.0		0.0	1.3	2.4		6.3	0.0	4.9	1.2	0.0	5.0							
Ref. No.	IC2501																					
MODE	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20		
STOP	12.2	0.3	0.0	0.3	0.0	0.0	16.2	0.0	2.9	1.7	1.6	0.7	1.5	2.4	2.5	2.5	2.5	1.3	5.0	3.5		
PLAY	12.3	4.8	0.0	4.8	0.0	0.0	16.3	0.0	2.8	1.7	1.7	0.7	1.4	2.4	2.5	2.5	2.5	1.3	5.0	3.6		
REC	12.2	0.5	0.0	0.9	0.0	0.0	16.3	0.0	2.9	1.6	1.7	0.7	1.5	2.4	2.5	2.5	2.5	1.3	5.0	3.5		
F.F	12.2	0.3	0.0	0.3	0.0	0.0	16.2	0.0	2.9	1.7	1.7	0.7	1.5	2.4	2.5	2.5	2.5	1.3	5.0	3.5		
REW	12.3	0.4	0.0	0.4	0.0	0.0	16.2	0.0	2.8	1.7	1.7	0.7	1.5	2.4	2.5	2.5	2.5	1.3	5.0	3.9		
Ref. No.	IC2501																					
MODE	21	22	23	24	25																	
STOP	12.2	3.5	3.5	0.0	3.5																	
PLAY	12.3	3.6	3.6	0.1	3.6																	
REC	12.2	3.6	3.5	0.0	3.6																	
F.F	12.3	3.5	3.5	0.0	3.5																	
REW	12.3	3.6	3.8	0.1	3.6																	
Ref. No.	IC6001																					
MODE	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20		
STOP	0.0	2.5	5.0	4.9	3.9	2.6	4.9	0.0	0.1	0.1	0.0	5.1	0.0	5.1	0.0	0.0	4.9	0.0	0.0	0.0		
PLAY	0.0	2.5	5.0	4.9	3.9	2.6	5.1	0.0	1.9	0.1	4.9	5.1	0.0	5.1	0.0	0.0	4.9	4.9	2.5	2.5		
REC	0.0	2.5	5.0	4.9	3.9	2.6	5.0	0.0	0.0	0.1	4.9	5.1	0.0	5.1	0.0	0.0	4.9	2.5	0.0	0.0		
F.F	0.0	2.5	4.7	4.9	3.9	2.6	5.0	0.0	0.2	0.1	4.9	5.1	0.0	5.1	0.0	0.0	4.9	2.5	0.0	0.0		
REW	0.0	2.5	4.7	4.9	3.9	2.6	5.1	0.0	0.2	0.1	4.9	5.1	0.0	5.1	0.0	0.0	4.9	2.5	0.0	0.0		
Ref. No.	IC6001																					
MODE	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40		
STOP	0.0	4.9	0.0	0.0	0.0	0.0	0.0	0.0	4.3	0.0	4.9	4.9	4.9	4.9	1.6	1.6	4.9	-	-	0.0		
PLAY	0.0	4.9	0.0	0.0	0.0	0.0	0.0	0.0	4.3	0.0	4.9	4.9	0.0	5.0	1.8	1.7	5.0	-	-	0.0		
REC	0.0	4.9	0.0	4.9	0.0	0.0	0.0	0.0	4.3	0.0	4.9	4.9	0.0	4.9	1.6	1.6	4.9	-	-	0.0		
F.F	0.0	4.9	0.0	0.0	0.0	0.0	0.0	0.0	4.3	4.9	4.9	0.0	0.0	4.9	1.6	1.6	4.9	-	-	0.0		
REW	0.0	4.9	0.0	0.0	0.0	0.0	0.0	0.0	4.3	4.9	4.9	0.0	0.0	4.9	1.6	1.6	4.9	-	-	0.0		
Ref. No.	IC6001																					
MODE	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60		
STOP	4.4	0.1	0.0	4.8	4.8	0.0	1.5	2.2	0.0	2.3	0.0	2.3	5.1	2.1	1.7	2.0	0.0	0.6	0.0	0.2		
PLAY	4.3	0.1	0.0	4.8	4.8	0.0	1.5	2.2	0.0	2.3	0.0	2.3	5.2	2.1	1.8	2.0	0.0	0.7	0.0	0.2		
REC	4.4	0.1	0.0	4.7	4.7	0.0	1.5	2.2	0.0	2.3	0.0	2.3	5.1	2.1	1.8	2.0	0.0	0.8	0.0	0.2		
F.F	4.4	0.1	0.0	3.0	3.0	0.0	1.5	2.2	0.0	2.3	0.0	2.3	5.2	2.1	1.7	2.0	0.0	0.6	0.0	0.2		
REW	4.4	0.1	0.0	3.0	3.0	0.0	1.5	2.2	0.0	2.3	0.0	2.3	5.2	2.1	2.2	2.0	0.0	0.6	0.0	0.2		
Ref. No.	IC6001																					
MODE	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80		
STOP	0.0	0.0	0.0	0.0	3.0	0.0	0.0	4.0	4.0	4.3	4.0	3.8	2.4	0.0	0.0	0.0	2.4	5.1	4.8	5.0		
PLAY	0.0	4.9	0.0	0.0	3.0	0.0	0.0	4.0	4.0	4.3	4.0	3.8	2.5	0.0	0.0	2.5	2.4	5.2	5.0	3.4		
REC	0.0	0.0	0.0	0.0	3.0	0.0	0.0	4.1	4.1	4.3	4.0	3.8	2.4	0.0	0.0	2.5	2.4	5.1	4.8	3.3		
F.F	0.0	0.0	0.0	0.0	3.0	0.0	0.0	4.1	4.1	4.3	4.0	3.8	2.4	0.0	0.0	2.7	2.4	5.1	2.2	2.3		
REW	0.0	0.0	0.0	0.0	3.0	0.0	0.0	4.1	4.1	4.3	4.0	3.8	2.4	4.9	0.0	3.1	2.4	5.1	2.5	2.5		
Ref. No.	IC6001																					
MODE	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100		
STOP	4.9	0.0	0.0	0.0	0.0	2.6	2.6	0.0	0.0	1.3	2.6	2.6	0.0	2.5	2.5	2.5	2.5	5.1	5.1	5.1		
PLAY	4.9	0.0	0.0	0.0	0.0	2.6	2.6	0.0	0.0	1.3	2.6	2.6	0.0	2.5	2.5	2.6	2.6	5.1	5.2	5.1		
REC	0.1	0.0	0.0	0.0	0.0	2.6	2.6	0.0	0.0	1.3	2.6	2.6	0.0	2.3	2.7	2.5	2.5	5.1	5.1	5.1		
F.F	4.9	1.7	0.0	0.0	0.0	2.6	2.6	0.0	0.0	1.3	2.6	2.6	0.0	2.5	2.5	2.6	2.5	5.1	5.1	5.1		
REW	4.9	0.0	0.0	0.0	0.0	2.6	2.6	0.0	0.0	1.3	2.6	2.6	0.0	2.5	2.5	2.6	2.7	5.2	5.2	5.1		
Ref. No.	IC6002					IC6003																
MODE	1	2	3	4	5		1	2	3													
STOP	5.1	5.1	0.0	-	-		5.1	0.0	5.1													
PLAY	5.2	5.1	0.0	-	-		5.1	0.0	5.1													
REC	5.1	5.1	0.0	-	-		5.1	0.0	5.1													
F.F	5.2	5.2	0.0	-	-		5.1	0.0	5.1													
REW	5.1	5.2	0.0	-	-		5.1	0.0	5.1													

SYSTEM CONTROL & SERVO TRs DC VOLTAGE CHART (SP MODE)

[illegible]