

5 CHECK INPUT AND OUTPUT VOLTAGE OF THE P.C BOARD

1. Before replace P.C Board, check input and output voltage of the P.C Board.
2. Check range of the test meter.
3. When check output voltage of the P.C Board, set a program of the Washing Machine on the working mode.
4. In case of measuring the motor circuit, Confirm all of 3 combinations (Red-Purple, Red-Blue and Blue-Purple) whether normal conditions or not.
5. In case of measuring push switch circuit, It shall not be pressed Power-ON button measured AC 100V, And press Power-ON button once to change AC 0V.
6. Measure each resistance after removed connectors from P.C Board w/ component.

