

Model: Schmidt 1		Date: 31-Aug-99	No.: RH545006
Subject: New Model (Schmidt1 Light)		Prepared by: K. Misugi	
From: Technical Service Dept., GTS Division			
Classification:	<input type="checkbox"/> Troubleshooting	<input type="checkbox"/> Part information	<input type="checkbox"/> Action required
	<input type="checkbox"/> Mechanical	<input type="checkbox"/> Electrical	<input type="checkbox"/> Service manual revision
	<input type="checkbox"/> Paper path	<input type="checkbox"/> Transmit/receive	<input type="checkbox"/> Retrofit information
	<input checked="" type="checkbox"/> Other (New Model Release Information)		

The new model Schmidt1 Light (FAX1900L) will be released in the line-up of the Schmidt1 (FAX2000L) series.

This technical bulletin is to inform the differences between the Schmidt1 Light and the Schmidt1. They are listed in order of sections that appear in the service manual.

## 1. OVERALL MACHINE INFORMATION

### 1.1. SPECIFICATIONS

Item	Schmidt1	Schmidt1 Light
2 MB Memory (Optional)	Available	Not Available Only 1 MB memory option is available for the Schmidt1 Light.
Multi-purpose Feeder (Optional)	Available	Not Available
Paper Feed Unit (Optional)	Available	Not Available
Print Resolutions Printer Mode	600 x 600 dpi	PC option is not available
Dimensions (W x D x H)	399 x 730 x 323 mm	399 x 604 x 299 mm The extension trays are not available in the Schmidt1 Light.

Model: Schmidt 1	Date: 31-Aug-99	No.: RH545006
------------------	-----------------	---------------

**1.2. FEATURES**

Features Comparison Table

<b>Features</b>	<b>Schmidt1</b>	<b>Schmidt1 Light</b>
<b>Equipment</b>		
Optional cassette (Multi-purpose feeder)	Available	Not available
Optional paper feed unit	Available	Not available
Optional printer interface	Available	Not available
Extension trays (Both document and paper trays: not listed in the features list.)	Available	Not available
<b>Communication Features</b>		
Batch transmission	Max 35 files	Not available
<b>Other User Features</b>		
Center mark	Available	Not available
Quick dial label printing	Available	Not available
Specified cassette selection	Available	Not available
Blank Document Detection (Not listed in the features list.)	Available	Not available

**2. DETAILED SECTION DESCRIPTIONS**

**2.1 SCANNER**

Scanning Speed

The scanning speed (during memory tx) for each resolution is as described below. Please note that this description is not mentioned in the Schmidt1 service manual.

<b>Resolution</b>	<b>Scan Speed (A4)</b>	
	<b>Schmidt1</b>	<b>Schmidt1 Light</b>
Standard	2.8 s	5.6 s
Detail	5.6 s	5.6 s
Fine	11.3 s	11.3 s

Model: Schmidt 1	Date: 31-Aug-99	No.: RH545006
------------------	-----------------	---------------

### 3. PARTS CATALOG INFORMATION

The following parts for the Schmidt1 Light are different from the Schmidt1.

Index	Schmidt1	Schmidt1 Lite	Description
3-3	H5454315	Not used	Document Tray Extension
3-16	H5454314	Not used	Document Table Extension
3-25	H5452131	Not used	Copy Tray Extension
3-26	H5456080	Not used	PC I/F Board
3-27	G0121165	Not used	Knob Screw
3-34	H5517258	Not used	Ferrite Core
5-1	H5454602	H5454617	Operation Panel Ass'y - Lite (RIC-EUR)
5-1	H5454606	H5454616	Operation Panel Ass'y - Lite (Infotec)
17-28	H5455116	Not used	Main Harness - Multi-purpose
19-22	H5454101	H5474101	Right Side Plate
21-13	H5456130	H5456136	PCB - FCU - Lite
21-13	H5456135	H5456136	PCB - FCU - Lite
23-16	H5454213	Not used	Decal - Parallel
23-20	H5455115 (modified to H5455137)	Not used	Main Harness - 2nd
25-13	H5453128	H5453204	Paper Feed Bracket - Lite
25-22	H5453189	H5473189	Magnetic Clutch Bracket
25-24	H5453174	Not used	Idler Gear 2 - 14Z
25-25	H5453173	Not used	Idler Gear 1 - 23Z
25-26	H5453171	Not used	Gear 2 - 31Z
25-27	H5453172	Not used	Gear 3 - 16Z
25-29	H5453130	Not used	Idle Gear - 2 nd – 24Z
21-	---	H5453199	Slow Down Gear - Lite



Model: Schmdit 1

Date: 31-Aug-99

No.: RH545006

**4. PRODUCT INFORMATION**

The Schmdit1 Lite is available only in the European market.

<b>Model Code</b>	<b>Model Name</b>	<b>Product Code</b>	<b>Serial #</b>
Schmidt1 Lite (EUR)	FAX1900L	H545-41	A12 Y MM 00001
Schmidt1 Lite (FRA)	FAX1900L	H545-44	A13 Y MM 00001
Schmidt1 Lite (INFO)	INFOTEC 3683L	H545-31	4C9 MM Y 0001
Schmidt1 Lite (INFO FRA)	INFOTEC 3683L	H545-34	4C9 MM Y 9001

RC	REBV	ASIA	
	*		