

R&S® ETL TV Analyzer

Installation Instructions for Options

Requirements

- The latest firmware version (2112.0740.00) must be installed on your R&S ETL. If you need to update your firmware, follow the instructions in the release notes.
- For information on options that must be installed refer to the R&S Home Page.

Installing the License Code Using the Graphical User Interface

You can perform the following steps using manual or remote operation. For details on the operating concepts refer to the user manual of the R&S ETL.

1. Press the "Setup" hardkey.
2. Press the following softkey sequence: "More" → "Option Licenses" → "Install Option"
An edit dialog box is displayed.
3. Enter the license code from the software option list supplied with the option and press "ENTER" to confirm the entry.
If the license code is not accepted, an error message is displayed. You need to repeat this step using the correct license code.
4. Reboot the R&S ETL to activate the option. If you want to install more than one option, you can enter all the license codes by reopening the dialog for each license code and reboot the R&S ETL afterwards only once.

Installing the Library

If the transport stream files are supplied together with a new R&S ETL, the files and the license key are already installed. To install the transport stream files on your R&S ETL, proceed as follows.

1. Copy the transport stream files from the DVD to USB stick, external USB HDD, or use the DVD with an external USB DVD drive.
2. Connect the USB stick, USB HDD or the external USB DVD drive to USB connector of the R&S ETL.
3. Copy the main folder and its contents from your library disc(s) to the "D:\\" directory.

© 2012 Rohde & Schwarz GmbH & Co. KG

Muehldorfstr. 15, 81671 Munich, Germany

Phone: +49 89 41 29 - 0

Fax: +49 89 41 29 12 164

E-mail: <mailto:info@rohde-schwarz.com>

Internet: <http://www.rohde-schwarz.com/>

R&S® is a registered trademark of Rohde & Schwarz GmbH & Co. KG.

Trade names are trademarks of the owners.



2115.1647.02 – 01

