

Model: HCD-D270, HCD-G3100

No. 530

Subject: Unit Dead, Power Amp IC Shorted.

Date: May 23, 1997

Symptom:

(111) The unit dead and/or IC1201 shorted. Main fuse could be open.

Solution:

If a unit comes in for service with any of the above symptoms, or for any other reason, replace the following resistors in the Power Amp Board as in indicated.

REF	FORMER		NEW	
	DESCRIPTION	PART NUMBER	DESCRIPTION	PART NUMBER
R1210, R1260	0.1Ω WIRE WOUND 10% 2W	1-208-601-11	0.22Ω WIRE WOUND 5W	1-217-156-00
R1212, R1262	22KΩ CARBON 5% 1/4W	1-247-863-91	15KΩ CARBON	1-249-431-11

