## SONY

## **Computer Monitors** Service Bulletin

CSI-111

Sony Service Company - Technical Services A Division of Sony Electronics Inc. Sony Drive, Park Ridge, New Jersey 07656

Model: GDM17SE1

60

Subject: Aging Mode

Date: June 24, 1994


Symptom: (\*\*\*)

How do you put this unit into Aging Mode?

Solution:

Before Performing White Balance, you must place the unit into aging for 30 minutes. To Place this unit into Aging you must do the following:

- 1. Remove the R,  $\mathbf{G}_{\mathbf{r}}\mathbf{B}\mathbf{, H}\mathbf{, and V}$  signal connections from the unit.
- 2. Power ON the unit and wait for it to go into POWER SAVE (Power Save LED Comes ON).
- 3. Press and Hold the CTRL and POWER Buttons for 2 seconds then release. The Green Power LED will flash.



4. To exit the Aging Mode, Power OFF the unit.

Reference: CM\_SE1AGING.DOC AUTOFLAGGED - NO



PRINTED IN USA