Lock-In Preamplifier

SR554 — Transformer preamplifier



· Transformer-coupled input

- 0.1 nV/ \sqrt{Hz} input noise
- · 0.1 Hz to 40 kHz bandwidth
- · Gain of 100 or 500
- · Single-ended and differential inputs
- ·>40 dB isolation from DC to 500 MHz
- · Powered by any SRS lock-in amplifier

· SR554 ... \$995 (U.S. list)

SR554 Transformer Preamplifier

The SR554 is a low-noise, transformer-coupled preamplifier optimized for source impedances between 0.05 Ω and 1 k Ω . With an input noise of only 0.1 nV/ $\sqrt{\rm Hz}$, the SR554 can be used in a wide range of low-noise applications. It is the ideal preamplifier for low-temperature synchronous detection applications where isolation between the experimental sample and the lock-in amplifier is critical.

The SR554 can operate in one of two modes. In the "bypassed" mode, the instrument is simply a passive transformer with a turns ratio of 100, providing an overall voltage gain of 100. In the "non-bypassed" mode, an additional amplifier (gain of 5) is added, increasing the overall gain to 500 and providing a low-impedance (<1 Ω) output. In the bypassed mode, the SR554 requires no external power. When using the output amplifier, ± 20 VDC must be supplied. The preamplifier connector on any SRS lock-in can be used to power the SR554.

Specifications

Mode Single-ended or differential

 $0.1 \text{ nV}/\sqrt{\text{Hz}}$ Noise

Source impedance 0.05Ω to 1 k Ω (recommended)

>120 dB below 1 kHz **CMRR**

Primary can float to $\pm 100 \ VDC$ Common mode range Gain

100× (transformer only) 500× (transformer and buffer)

Max. freq. response 0.1 Hz to 40 kHz

>40 dB, DC to 500 MHz Isolation Single-ended or differential Output Maximum output 100 Vpp (transformer only)

20 Vpp (transformer and buffer)

Output impedance $>5 k\Omega$ (transformer only) $<1 \Omega$ (transformer and buffer)


 $3.75" \times 3" \times 7.5"$ (WHD) Dimensions

Weight 4 lbs.

Warranty One year parts and labor on defects

in materials and workmanship

SR554 Noise Figure Contours



Ordering Information

SR554 Transformer preamplifier \$995

