

Technical Information 51/75

COMPATIBILITY LIST

A80/VU-Multi-Channel Amplifier

Description		Use in VU-Amplifier		
		MK I	24 Channel Intermediate	MK II
Amplifier mother board	1.080.880	x		
Amplifier mother board	1.080.877		x	
Amplifier mother board	1.080.800			x
Record driver amplifier	1.080.801		x	x
Record driver amplifier	1.080.881	x		
Record preamplifier	1.080.802		x	x
Record equalizer card				
7.5/15"	1.080.867		x	x
15/30"	1.080.873		x	x
Record preamplifier	1.080.882	x		
Reproduce/sync. preamplifier	1.080.805		x	x
Reproduce/sync. preamplifier	1.080.804		x	x
Reproduce equalizer card				
7.5/15"	1.080.865		x	x
15/30"	1.080.875		x	x
Sync. equalizer card (24 ch)				
7.5/15"	1.080.864		x	x
Sync. equalizer card (standard)				
7.5/15"	1.080.866		x	x
15/30"	1.080.874		x	x
Reproduce preamplifier	1.080.885	x		
Sync. preamplifier	1.080.884	x		
Programmer PC	1.080.809			x
Programmer PC	1.080.810			x
Programmer PC	1.080.812			x
Control logic	1.080.883	x	x	x
Control logic	1.080.803	x	x	x

COMPATIBILITY LIST

Description	Use in VU-Amplifier		
	MK I	24 Channel Intermediate	MK II
Reproduce/Sync Line Amplifier 1.080.886	x	x	x
Reproduce/Sync Line Amplifier 1.080.806	x	x	x
VU-Meter Plug-in Module 1.080.887	x	x	x
VU-Meter Plug-in Module 1.080.807	x	x	x
Record Equalisation Plug-in Module 1.080.890	x	x	x
Reproduce Equalisation Plug-in Module 1.080.889	x	x	x

Programmer PC 1.080.809					Programmer PC 1.080.810				
Switch Position	Repro. o/p	Sync. o/p	Ready Lamp	Record Lamp	Switch Position	Repro. o/p	Sync. o/p	Ready Lamp	Record Lamp
Sync	Sync	Sync	--	--	Sync	Sync	Sync	--	--
Safe	Repro	Sync	--	--	Safe	Repro	Sync	--	--
Ready	Repro	Input	x	--	Ready	Repro	Input	x	--
Ready/Rec	Repro	Input	--	x	Ready/Rec	Repro	Input	--	x
Not to be used in connection with STUDER Remote control					To be used in connection with STUDER Remote control				

Programmer PC 1.080.812				
Switch Position	Repro o/p	Sync. o/p	Ready Lamp	Record Lamp
Sync	Sync	Sync	--	--
Safe	Repro	Sync	--	--
Ready	Repro	Sync	x	--
Ready/Rec	Repro	Input	--	x