

REPLACEABLE ELECTRICAL PARTS

PARTS ORDERING INFORMATION

Replacement parts are available from or through your local Tektronix, Inc. Field Office or representative.

Changes to Tektronix instruments are sometimes made to accommodate improved components as they become available, and to give you the benefit of the latest circuit improvements developed in our engineering department. It is therefore important, when ordering parts, to include the following information in your order: Part number, instrument type or number, serial number, and modification number if applicable.

If a part you have ordered has been replaced with a new or improved part, your local Tektronix, Inc. Field Office or representative will contact you concerning any change in part number.

Change information, if any, is located at the rear of this manual.

SPECIAL NOTES AND SYMBOLS

X000 Part first added at this serial number
00X Part removed after this serial number

ITEM NAME

In the Parts List, an Item Name is separated from the description by a colon (:). Because of space limitations, an Item Name may sometimes appear as incomplete. For further Item Name identification, the U.S. Federal Cataloging Handbook H6-1 can be utilized where possible.

ABBREVIATIONS

ACTR	ACTUATOR	PLSTC	PLASTIC
ASSY	ASSEMBLY	QTZ	QUARTZ
CAP	CAPACITOR	RECP	RECEPTACLE
CER	CERAMIC	RES	RESISTOR
CKT	CIRCUIT	RF	RADIO FREQUENCY
COMP	COMPOSITION	SEL	SELECTED
CONN	CONNECTOR	SEMICOND	SEMICONDUCTOR
ELCTLT	ELECTROLYTIC	SENS	SENSITIVE
ELEC	ELECTRICAL	VAR	VARIABLE
INCAND	INCANDESCENT	WW	WIREWOUND
LED	LIGHT EMITTING DIODE	XFMR	TRANSFORMER
NONWIR	NON WIREWOUND	XTAL	CRYSTAL

CROSS INDEX—MFR. CODE NUMBER TO MANUFACTURER

Mfr. Code	Manufacturer	Address	City, State, Zip
0000L	MATSUSHITA ELECTRIC	200 PARK AVENUE, 54TH FLOOR	NEW YORK, NY 10017
0000W	UNITED CHEMICON, INC.	731 JAMES STREET	SYRACUSE, NY 13203
00853	SANGAMO ELECTRIC CO., S. CAROLINA DIV.	P O BOX 128	PICKENS, SC 29671
01002	GENERAL ELECTRIC COMPANY, INDUSTRIAL AND POWER CAPACITOR PRODUCTS DEPARTMENT	JOHN STREET	HUDSON FALLS, NY 12839
01121	ALLEN-BRADLEY COMPANY	1201 2ND STREET SOUTH	MILWAUKEE, WI 53204
01295	TEXAS INSTRUMENTS, INC., SEMICONDUCTOR GROUP	P O BOX 5012, 13500 N CENTRAL EXPRESSWAY	DALLAS, TX 75222
02111	SPECTROL ELECTRONICS CORPORATION	17070 EAST GALE AVENUE	CITY OF INDUSTRY, CA 91745
02735	RCA CORPORATION, SOLID STATE DIVISION	ROUTE 202	SOMERVILLE, NY 08876
02777	HOPKINS ENGINEERING COMPANY	12900 FOOTHILL BLVD.	SAN FERNANDO, CA 91342
03508	GENERAL ELECTRIC COMPANY, SEMI-CONDUCTOR PRODUCTS DEPARTMENT	ELECTRONICS PARK	SYRACUSE, NY 13201
03888	KDI PYROFILM CORPORATION	60 S JEFFERSON ROAD	WHIPPANY, NJ 07981
04222	AVX CERAMICS, DIVISION OF AVX CORP.	P O BOX 867, 19TH AVE. SOUTH	MYRTLE BEACH, SC 29577
04713	MOTOROLA, INC., SEMICONDUCTOR PROD. DIV.	5005 E MCDOWELL RD, PO BOX 20923	PHOENIX, AZ 85036
08806	GENERAL ELECTRIC CO., MINIATURE LAMP PRODUCTS DEPARTMENT	NELA PARK	CLEVELAND, OH 44112
12697	CLAROSTAT MFG. CO., INC.	LOWER WASHINGTON STREET	DOVER, NH 03820
12969	UNITRODE CORPORATION	580 PLEASANT STREET	WATERTOWN, MA 02172
14099	SEMTECH CORP.	652 MITCHELL RD.	NEWBURY PARK, CA 91320
14752	ELECTRO CUBE INC.	1710 S. DEL MAR AVE.	SAN GABRIEL, CA 91776
14936	GENERAL INSTRUMENT CORP., SEMICONDUCTOR PRODUCTS GROUP	P.O. BOX 600, 600 W. JOHN ST.	HICKSVILLE, NY 11802
15454	RODAN INDUSTRIES, INC.	2905 BLUE STAR ST.	ANAHEIM, CA 92806
16546	U.S. CAPACITOR CORP/CENTRALAB ELECTRONICS DIV.	4561 COLORADO	LOS ANGELES, CA 90039
18324	SIGNETICS CORP.	811 E. ARQUES	SUNNYVALE, CA 94086
19701	ELECTRA-MIDLAND CORP., MEPCO ELECTRA INC.	P O BOX 760	MINERAL WELLS, TX 76067
23223	CTS MICROELECTRONICS, INC.	1201 CUMBERLAND AVENUE P O BOX 1278	WEST LAFAYETTE, IN 47902
24546	CORNING GLASS WORKS, ELECTRONIC COMPONENTS DIVISION	550 HIGH STREET	BRADFORD, PA 16701
25088	SIEMENS CORP.	186 WOOD AVE. S	ISELIN, NJ 08830
27014	NATIONAL SEMICONDUCTOR CORP.	2900 SEMICONDUCTOR DR.	SANTA CLARA, CA 95051
28480	HEWLETT-PACKARD CO., CORPORATE HQ.	1501 PAGE MILL RD.	PALO ALTO, CA 94304
32997	BOURNS, INC., TRIMPOT PRODUCTS DIV.	1200 COLUMBIA AVE.	RIVERSIDE, CA 92507
50157	MIDWEST COMPONENTS INC.	P. O. BOX 787 1981 PORT CITY BLVD.	MUSKEGON, MI 49443
50434	HEWLETT-PACKARD COMPANY	640 PAGE MILL ROAD	PALO ALTO, CA 94304
50558	ELECTRONIC CONCEPTS, INC.	526 INDUSTRIAL WAY WEST	EATONTOWN, NJ 07724
53184	XCITON CORPORATION	5 HEMLOCK STREET	LATHAM, NY 12110
53944	ELT INC., GLOW LITE DIVISION	BOX 698	PAULS VALLEY, OK 73075
54473	MATSUSHITA ELECTRIC, CORP. OF AMERICA	1 PANASONIC WAY	SECAUCUS, NJ 07094
55680	NICHICON/AMERICA/CORP.	6435 N PROESEL AVENUE	CHICAGO, IL 60645
56289	SPRAGUE ELECTRIC CO.		NORTH ADAMS, MA 01247
71400	BUSSMAN MFG., DIVISION OF MCGRAW-EDISON CO.	2536 W. UNIVERSITY ST.	ST. LOUIS, MO 63107
71590	CENTRALAB ELECTRONICS, DIV. OF GLOBE-UNION, INC.	P O BOX 858	FORT DODGE, IA 50501
72982	ERIE TECHNOLOGICAL PRODUCTS, INC.	644 W. 12TH ST.	ERIE, PA 16512
73138	BECKMAN INSTRUMENTS, INC., HELIPOT DIV.	2500 HARBOR BLVD.	FULLERTON, CA 92634
73899	JFD ELECTRONICS COMPONENTS CORP.	PINETREE ROAD	OXFORD, NC 27565
75042	TRW ELECTRONIC COMPONENTS, IRC FIXED RESISTORS, PHILADELPHIA DIVISION	401 N. BROAD ST.	PHILADELPHIA, PA 19108
76493	BELL INDUSTRIES, INC., MILLER, J. W., DIV.	19070 REYES AVE., P O BOX 5825	COMPTON, CA 90224
77342	AMF INC., POTTER AND BRUMFIELD DIV.	200 RICHLAND CREEK DRIVE	PRINCETON, IN 47671
79727	C-W INDUSTRIES	550 DAVISVILLE RD., P O BOX 96	WARMINSTER, PA 18974
80009	TEKTRONIX, INC.	P O BOX 500	BEAVERTON, OR 97077
80031	ELECTRA-MIDLAND CORP., MEPCO DIV.	22 COLUMBIA ROAD	MORRISTOWN, NJ 07960
81073	GRAYHILL, INC.	561 HILLGROVE AVE., PO BOX 373	LA GRANGE, IL 60525
81483	INTERNATIONAL RECTIFIER CORP.	9220 SUNSET BLVD.	LOS ANGELES, CA 90069

CROSS INDEX—MFR. CODE NUMBER TO MANUFACTURER

Mfr. Code	Manufacturer	Address	City, State, Zip
82389	SWITCHCRAFT, INC.	5555 N. ELSTON AVE.	CHICAGO, IL 60630
84411	TRW ELECTRONIC COMPONENTS, TRW CAPACITORS	112 W. FIRST ST.	OGALLALA, NE 69153
87034	ILLUMINATED PRODUCTS INC., A SUB OF OAK INDUSTRIES, INC.	2620 SUSAN ST, PO BOX 11930	SANTA ANA, CA 92711
90201	MALLORY CAPACITOR CO., DIV. OF P. R. MALLORY AND CO., INC.	3029 E WASHINGTON STREET P O BOX 372	INDIANAPOLIS, IN 46206 COLUMBUS, NE 68601
91637	DALE ELECTRONICS, INC.	P. O. BOX 609	
93410	ESSEX INTERNATIONAL, INC., CONTROLS DIV. LEXINGTON PLANT	P. O. BOX 1007	MANSFIELD, OH 44903
99699	DEUTSCH RELAYS, INC.	65 DALY ROAD	EAST NORTHPORT, LI, NY 11731

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff Dscont	Name & Description	Mfr Code	Mfr Part Number
A1	670-4895-00		CKT BOARD ASSY:FRONT PANEL	80009	670-4895-00
A2	670-5227-00		CKT BOARD ASSY:DISPLAY CONTROL	80009	670-5227-00
A3	670-4778-00		CKT BOARD ASSY:TRIGGER LIGHT	80009	670-4778-00
A4	670-4778-00		CKT BOARD ASSY:TRIGGER LIGHT	80009	670-4778-00
A5	670-4773-00		CKT BOARD ASSY:MODE SWITCH	80009	670-4773-00
A6	670-4775-00		CKT BOARD ASSY:MAIN INTERFACE	80009	670-4775-00
A7	670-5098-00		CKT BOARD ASSY:FOLLOWER,TRIG OUT 'A'	80009	670-5098-00
A8	670-5099-00		CKT BOARD ASSY:FOLLOWER,TRIG OUT 'B'	80009	670-5099-00
A9	670-5617-00		CKT BOARD ASSY:FOLLOWER,HORIZ AMP 'B'	80009	670-5617-00
A10	670-5096-00		CKT BOARD ASSY:FOLLOWER,HORIZ AMP 'A'	80009	670-5096-00
A11	670-5097-00		CKT BOARD ASSY:FOLLOWER,VERT CHANNEL	80009	670-5097-00
A12	670-5097-00		CKT BOARD ASSY:FOLLOWER,VERT CHANNEL	80009	670-5097-00
A13	670-4777-00		CKT BOARD ASSY:LOGIC	80009	670-4777-00
A14	670-4776-00		CKT BOARD ASSY:TRIGGER SELECT	80009	670-4776-00
A15	670-1900-03		CKT BOARD ASSY:READOUT	80009	670-1900-03
A16	670-4769-00		CKT BOARD ASSY:VERTICAL CHANNEL SW	80009	670-4769-00
A17	670-4770-00		CKT BOARD ASSY:VERTICAL AMPLIFIER	80009	670-4770-00
A18	670-4779-00		CKT BOARD ASSY:CRT TERMINATOR	80009	670-4779-00
A19	670-4771-00		CKT BOARD ASSY:HORIZONTAL AMPLIFIER	80009	670-4771-00
A20	670-0702-03		CKT BOARD ASSY:GRATICULE	80009	670-0702-03
A21	670-4774-00		CKT BOARD ASSY:Z-AXIS	80009	670-4774-00
A22	670-4772-00		CKT BOARD ASSY:HIGH VOLTAGE	80009	670-4772-00
A23	670-5638-00		CKT BOARD ASSY:CONTROL/RECTIFIER	80009	670-5638-00
A24	670-5639-00		CKT BOARD ASSY:LOW VOLTAGE RECTIFIER	80009	670-5639-00
A25	670-2245-01		CKT BOARD ASSY:FAN	80009	670-2245-01
A27	670-4346-00		CKT BOARD ASSY:READOUT PROTECTION #1	80009	670-4346-00
A27	-----		* OPTION 2 ONLY		
A28	670-4780-00		CKT BOARD ASSY:X-Y DELAY COMPENSATION	80009	670-4780-00
A29	670-5093-00		CKT BOARD ASSY:HORIZONTAL CRT FLEXCON	80009	670-5093-00
A30	670-5094-00		CKT BOARD ASSY:HORIZONTAL CRT FLEXCON	80009	670-5094-00
A31	670-5616-00		CKT BOARD ASSY:VERTIAL CRT FLEXCON	80009	670-5616-00
B1690	147-0035-00		MOTOR,DC:BRUSHLESS,10-15VDC,145MA	25088	1AD3001-0A
C2	290-0747-00		CAP.,FXD,ELCTLT:100UF,+50-10%,25V	56289	500D148
C3	285-0674-00		CAP.,FXD,PLASTIC:0.01UF,10%,100V	56289	410P10391
C4	290-0747-00		CAP.,FXD,ELCTLT:100UF,+50-10%,25V	56289	500D148
C5	285-0674-00		CAP.,FXD,PLASTIC:0.01UF,10%,100V	56289	410P10391
C6	290-0194-00		CAP.,FXD,ELCTLT:10UF,+50-10%,100V	56289	30D106F100DC4
C8	290-0194-00		CAP.,FXD,ELCTLT:10UF,+50-10%,100V	56289	30D106F100DC4
C9	290-0747-00		CAP.,FXD,ELCTLT:100UF,+50-10%,25V	56289	500D148
C71	281-0547-00		CAP.,FXD,CER DI:2.7PF,10%,500V	72982	301-000C0J0279C
C85	283-0111-00		CAP.,FXD,CER DI:0.1UF,20%,50V	72982	8121-N088Z5U104M
C87	283-0111-00		CAP.,FXD,CER DI:0.1UF,20%,50V	72982	8121-N088Z5U104M
C237	283-0221-00		CAP.,FXD,CER DI:0.47UF,20%,50V	72982	8131N087X7R0474M
C240	290-0183-00		CAP.,FXD,ELCTLT:1UF,10%,35V	56289	162D105X9035CD2
C250	290-0525-00		CAP.,FXD,ELCTLT:4.7UF,20%,50V	56289	196D475X0050KA1
C270	283-0177-00		CAP.,FXD,CER DI:1UF,+80-20%,25V	72982	8131N039 E 105Z
C324	283-0002-00		CAP.,FXD,CER DI:0.01UF,+80-20%,500V	72982	811-546E103Z
C325	283-0115-00		CAP.,FXD,CER DI:47PF,5%,200V	72982	805-519-COG0470J
C326	283-0002-00		CAP.,FXD,CER DI:0.01UF,+80-20%,500V	72982	811-546E103Z
C376	285-1006-00		CAP.,FXD,PLSTC:0.22UF,2%,50V	80009	285-1006-00
C384	283-0115-00		CAP.,FXD,CER DI:47PF,5%,200V	72982	805-519-COG0470J
C386	283-0115-00		CAP.,FXD,CER DI:47PF,5%,200V	72982	805-519-COG0470J

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Discont	Name & Description	Mfr Code	Mfr Part Number
C440	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C447	283-0221-00			CAP., FXD, CER DI: 0.47UF, 20%, 50V	72982	8131N087X7R0474M
C450	290-0788-00			CAP., FXD, ELCTLT: 220UF, 20%, 35V	56289	39D793
C483	281-0513-00			CAP., FXD, CER DI: 27PF, +/-5.4PF, 500V	72982	301-000P2G0270M
C486	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C487	283-0111-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8121-N088Z5U104M
C488	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C490	283-0339-00			CAP., FXD, CER DI: 0.22UF, 10%, 50V	72982	8131N075W5R224K
C493	281-0513-00			CAP., FXD, CER DI: 27PF, +/-5.4PF, 500V	72982	301-000P2G0270M
C505	281-0811-00			CAP., FXD, CER DI: 10PF, 10%, 100V	72982	8035D2AADC1G100K
C508	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C512	285-0650-00			CAP., FXD, PLSTC: 0.027UF, 5%, 100V	56289	410P104
C515	285-0643-00			CAP., FXD, PLSTC: 0.0047UF, 5%, 100V	56289	410P103
C520	283-0666-00			CAP., FXD, MICA D: 890PF, 2%, 100V	00853	D151F891G0
C525	283-0649-00			CAP., FXD, MICA D: 105PF, 1%, 300V	00853	D153F1050F0
C531	285-0598-00			CAP., FXD, PLSTC: 0.01UF, 5%, 100V	01002	61F10AC103
C538	281-0204-00			CAP., VAR, PLSTC: 2-22PF, 100V	80031	287C00222MJ02
C539	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C582	290-0745-00			CAP., FXD, ELCTLT: 22UF, +50-10%, 25V	56289	502D225
C583	290-0745-00			CAP., FXD, ELCTLT: 22UF, +50-10%, 25V	56289	502D225
C584	290-0745-00			CAP., FXD, ELCTLT: 22UF, +50-10%, 25V	56289	502D225
C605	281-0811-00			CAP., FXD, CER DI: 10PF, 10%, 100V	72982	8035D2AADC1G100K
C608	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C612	285-0650-00			CAP., FXD, FLSTC: 0.027UF, 5%, 100V	56289	410P104
C615	285-0643-00			CAP., FXD, PLSTC: 0.0047UF, 5%, 100V	56289	410P103
C620	283-0666-00			CAP., FXD, MICA D: 890PF, 2%, 100V	00853	D151F891G0
C625	283-0649-00			CAP., FXD, MICA D: 105PF, 1%, 300V	00853	D153F1050F0
C631	285-0598-00			CAP., FXD, PLSTC: 0.01UF, 5%, 100V	01002	61F10AC103
C638	281-0204-00			CAP., VAR, PLSTC: 2-22PF, 100V	80031	287C00222MJ02
C639	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C675	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C681	281-0788-00			CAP., FXD, CER DI: 470PF, 10%, 100V	72982	8005H9AADW5R471K
C695	290-0746-00			CAP., FXD, ELCTLT: 47UF, +50-10%, 16V	56289	502D226
C705	281-0218-00			CAP., VAR, CER DI: 1-5PF, +2-2.5%, 100V	72982	513-001 1-5
C730	281-0814-00			CAP., FXD, CER DI: 100PF, 10%, 100V	72982	8005D2AADCOG101K
C751	283-0176-00			CAP., FXD, CER DI: 0.0022UF, 20%, 50V	56289	272C5
C762	283-0253-00			CAP., FXD, CER DI: 10UF, 10%, 50V	72982	A15BF9A4LW5R103K
C780	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C782	281-0810-00			CAP., FXD, CER DI: 5.6PF, 0.5%, 100V	72982	8035D2AADCOG569D
C783	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C787	285-0686-00			CAP., FXD, PLSTC: 0.068UF, 10%, 100V	56289	410P68391
C791	285-0643-00			CAP., FXD, PLSTC: 0.0047UF, 5%, 100V	56289	410P103
C795	283-0666-00			CAP., FXD, MICA D: 890PF, 2%, 100V	00853	D151F891G0
C801	283-0649-00			CAP., FXD, MICA D: 105PF, 1%, 300V	00853	D153F1050F0
C806	285-0683-00			CAP., FXD, PLSTC: 0.022UF, 5%, 100V	56289	410P22351
C808	281-0204-00			CAP., VAR, PLSTC: 2-22PF, 100V	80031	287C00222MJ02
C809	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C838	283-0334-00			CAP., FXD, CER DI: 130PF, +1-2%, 500V	72982	8121N501COG0131G
C852	283-0353-00			CAP., FXD, CER DI: 0.1UF, 10%, 50V	16546	W050FH104KPSS
C862	283-0353-00			CAP., FXD, CER DI: 0.1UF, 10%, 50V	16546	W050FH104KPSS
C878	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C881	283-0005-00			CAP., FXD, CER DI: 0.01UF, +100-0%, 250V	72982	8131N300Z5U0103P
C882	283-0005-00			CAP., FXD, CER DI: 0.01UF, +100-0%, 250V	72982	8131N300Z5U0103P

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C885	283-0178-00			CAP., FXD, CER DI: 0.1UF, +80-20%, 100V	72982	8131N145 E 104Z
C891	290-0768-00			CAP., FXD, ELCTLT: 10UF, +50-10%, 100V	54473	ECE-A100V10L
C893	290-0745-00			CAP., FXD, ELCTLT: 22UF, +50-10%, 25V	56289	502D225
C895	290-0776-00			CAP., FXD, ELCTLT: 22UF, +50-10%, 10V	0000L	ECE-A10V22L
C897	290-0745-00			CAP., FXD, ELCTLT: 22UF, +50-10%, 25V	56289	502D225
C944	281-0808-00			CAP., FXD, CER DI: 7PF, 20%, 100V	72982	8035D9AADC0G709G
C950	283-0597-00			CAP., FXD, MICA D: 470PF, 10%, 300V	00853	D153E471K0
C952	285-0813-00			CAP., FXD, PLSTC: 0.0015UF, 5%, 100V	14752	410D1B152J
C955	285-0598-00			CAP., FXD, PLSTC: 0.01UF, 5%, 100V	01002	61F10AC103
C958	285-0808-00			CAP., FXD, PLSTC: 0.1UF, 10%, 50V	56289	LP66A1A104K004
C974	281-0808-00			CAP., FXD, CER DI: 7PF, 20%, 100V	72982	8035D9AADC0G709G
C980	283-0597-00			CAP., FXD, MICA D: 470PF, 10%, 300V	00853	D153E471K0
C982	285-0813-00			CAP., FXD, PLSTC: 0.0015UF, 5%, 100V	14752	410D1B152J
C985	285-0598-00			CAP., FXD, PLSTC: 0.01UF, 5%, 100V	01002	61F10AC103
C988	285-0808-00			CAP., FXD, PLSTC: 0.1UF, 10%, 50V	56289	LP66A1A104K004
C1001	290-0769-00			CAP., FXD, ELCTLT: 10UF, +50-10%, 100V	0000W	100T10
C1002	290-0776-00			CAP., FXD, ELCTLT: 22UF, +50-10%, 10V	0000L	ECE-A10V22L
C1003	290-0745-00			CAP., FXD, ELCTLT: 22UF, +50-10%, 25V	56289	502D225
C1004	290-0745-00			CAP., FXD, ELCTLT: 22UF, +50-10%, 25V	56289	502D225
C1011	283-0110-00			CAP., FXD, CER DI: 0.005UF, +80-20%, 150V	56289	19C242B
C1017	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1019	290-0523-00			CAP., FXD, ELCTLT: 2.2UF, 20%, 20V	56289	196D225X0020HA1
C1035	281-0601-00			CAP., FXD, CER DI: 7.5PF, 500V	72982	301-000COH0759D
C1036	281-0203-00			CAP., VAR, PLSTC: 2-10PF, 100V	80031	2807C00210MJ02FO
C1040	281-0122-00			CAP., VAR, CER DI: 2.5-9PF, 100V	72982	518-000A2.5-9
C1044	281-0592-00			CAP., FXD, CER DI: 4.7PF, +/-0.5PF, 500V	72982	301-023COH0479D
C1060	281-0122-00			CAP., VAR, CER DI: 2.5-9PF, 100V	72982	518-000A2.5-9
C1064	281-0592-00			CAP., FXD, CER DI: 4.7PF, +/-0.5PF, 500V	72982	301-023COH0479D
C1073	281-0773-00			CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1075	283-0299-00			CAP., FXD, CER DI: 51PF, 5%, 500V	72982	8121N501COG510J
C1096	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1098	283-0178-00			CAP., FXD, CER DI: 0.1UF, +80-20%, 100V	72982	8131N145 E 104Z
C1110	283-0180-00			CAP., FXD, CER DI: 5600PF, 20%, 200V	72982	8121N204 E 562M
C1110	-----			* OPTION 2 ONLY		
C1112	283-0107-00			CAP., FXD, CER DI: 51PF, 5%, 200V	72982	8121B232C0G0510J
C1112	-----			* OPTION 2 ONLY		
C1113	283-0197-00			CAP., FXD, CER DI: 470PF, 5%, 100V	72982	8121N075C0G0471J
C1113	-----			* OPTION 2 ONLY		
C1114	281-0158-00			CAP., VAR, CER DI: 7-45PF, 50V	73899	DVJ-5006
C1114	-----			* OPTION 2 ONLY		
C1142	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C1142	-----			* OPTION 2 ONLY		
C1156	281-0619-00			CAP., FXD, CER DI: 1.2PF, +/-0.1PF, 200V	72982	374-000COK0129B
C1156	-----			* OPTION 2 ONLY		
C1165	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C1165	-----			* OPTION 2 ONLY		
C1205	283-0022-00			CAP., FXD, CER DI: 0.02UF, 1400VDCAC	80009	283-0022-00
C1206	283-0022-00			CAP., FXD, CER DI: 0.02UF, 1400VDCAC	80009	283-0022-00
C1216	290-0628-00			CAP., FXD, ELCTLT: 950UF, +50-10%, 200V	56289	36D7560
C1217	290-0628-00			CAP., FXD, ELCTLT: 950UF, +50-10%, 200V	56289	36D7560
C1219	283-0057-00			CAP., FXD, CER DI: 0.1UF, +80-20%, 200V	56289	274C10

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C1227	283-0280-00			CAP., FXD, CER DI: 2200PF, 10%, 2000V	56289	29C558
C1228	283-0280-00			CAP., FXD, CER DI: 2200PF, 10%, 2000V	56289	29C558
C1229	285-0939-00			CAP., FXD, PLSTC: 3UF, 5%, 400V	84411	TEK111-30594
C1231	290-0782-00			CAP., FXD, ELCTLT: 4.7UF, +75-10%, 35V	56289	503D475G035AS
C1236	283-0280-00			CAP., FXD, CER DI: 2200PF, 10%, 2000V	56289	29C558
C1237	285-0938-00			CAP., FXD, PLSTC: 0.03UF, 5%, 600V	56289	AF8B1G303J004
C1238	283-0279-00			CAP., FXD, CER DI: 0.001UF, 20%, 3000V	56289	55C153
C1239	290-0782-00			CAP., FXD, ELCTLT: 4.7UF, +75-10%, 35V	56289	503D475G035AS
C1242	283-0001-00			CAP., FXD, CER DI: 0.005UF, +100-0%, 500V	72982	831-559E502P
C1243	290-0767-00			CAP., FXD, ELCTLT: 4.7UF, +75-10%, 160V	56289	502D228
C1252	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1254	290-0573-00			CAP., FXD, ELCTLT: 2.7UF, 20%, 50V	56289	196D275X0050JA1
C1255	283-0028-00			CAP., FXD, CER DI: 0.0022UF, 20%, 50V	56289	19C606
C1264	290-0263-00			CAP., FXD, ELCTLT: 2.7UF, 15V	56289	162D275X9015CD2
C1266	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1267	290-0523-00			CAP., FXD, ELCTLT: 2.2UF, 20%, 20V	56289	196D225X0020HA1
C1270	290-0523-00			CAP., FXD, ELCTLT: 2.2UF, 20%, 20V	56289	196D225X0020HA1
C1271	290-0523-00			CAP., FXD, ELCTLT: 2.2UF, 20%, 20V	56289	196D225X0020HA1
C1274	283-0594-00			CAP., FXD, MICA D: 0.001UF, 1%, 100V	00853	D151F102F0
C1277	283-0060-00			CAP., FXD, CER DI: 100PF, 5%, 200V	72982	855-535U2J101J
C1278	283-0060-00			CAP., FXD, CER DI: 100PF, 5%, 200V	72982	855-535U2J101J
C1280	283-0080-00			CAP., FXD, CER DI: 0.022UF, +80-20%, 25V	56289	19C611
C1286	290-0580-00			CAP., FXD, ELCTLT: 0.27UF, 20%, 50V	56289	196D274X0050HA1
C1290	290-0778-00			CAP., FXD, ELCTLT: 1UF, +50-10%, 50V	0000L	ECE-A50N1
C1292	285-1123-00			CAP., FXD, PLASTIC: 1UF, 20%, 200V	50558	ME2-2190
C1294	285-0543-00			CAP., FXD, PLASTIC: 0.0022UF, 20%, 400V	56289	410P22204
C1324	290-0758-00			CAP., FXD, ELCTLT: 2.2UF, +50-10%, 160V	56289	502D227
C1325	290-0758-00			CAP., FXD, ELCTLT: 2.2UF, +50-10%, 160V	56289	502D227
C1327	285-0892-00			CAP., FXD, PLSTC: 0.22UF, 10%, 200V	56289	LP66A1C224K002
C1332	290-0768-00			CAP., FXD, ELCTLT: 10UF, +50-10%, 100V	54473	ECE-A100V10L
C1333	290-0768-00			CAP., FXD, ELCTLT: 10UF, +50-10%, 100V	54473	ECE-A100V10L
C1334	290-0768-00			CAP., FXD, ELCTLT: 10UF, +50-10%, 100V	54473	ECE-A100V10L
C1335	290-0768-00			CAP., FXD, ELCTLT: 10UF, +50-10%, 100V	54473	ECE-A100V10L
C1342	290-0772-00			CAP., FXD, ELCTLT: 330UF, +50-10%, 25V	0000L	ECE-B25Z330
C1343	290-0770-00			CAP., FXD, ELCTLT: 100UF, +50-10%, 25V	56289	502D230
C1344	290-0772-00			CAP., FXD, ELCTLT: 330UF, +50-10%, 25V	0000L	ECE-B25Z330
C1345	290-0770-00			CAP., FXD, ELCTLT: 100UF, +50-10%, 25V	56289	502D230
C1352	290-0771-00			CAP., FXD, ELCTLT: 220UF, +50-10%, 10VDC	0000L	ECE-A10V220L
C1353	290-0771-00			CAP., FXD, ELCTLT: 220UF, +50-10%, 10VDC	0000L	ECE-A10V220L
C1354	290-0754-00			CAP., FXD, ELCTLT: 2200UF, +75-10%, 10VDC	56289	432D222010AA2
C1355	290-0773-00			CAP., FXD, ELCTLT: 1000UF, +50-10%, 10V	0000L	ECE-B10Z1000
C1356	290-0771-00			CAP., FXD, ELCTLT: 220UF, +50-10%, 10VDC	0000L	ECE-A10V220L
C1371	290-0746-00			CAP., FXD, ELCTLT: 47UF, +50-10%, 16V	56289	502D226
C1374	283-0221-00			CAP., FXD, CER DI: 0.47UF, 20%, 50V	72982	8131N087X7R0474M
C1408	290-0778-00			CAP., FXD, ELCTLT: 1UF, +50-10%, 50V	0000L	ECE-A50N1
C1412	290-0778-00			CAP., FXD, ELCTLT: 1UF, +50-10%, 50V	0000L	ECE-A50N1
C1415	281-0629-00			CAP., FXD, CER DI: 33PF, 5%, 600V	72982	308-000C0G0330J
C1417	290-0778-00			CAP., FXD, ELCTLT: 1UF, +50-10%, 50V	0000L	ECE-A50N1
C1424	283-0110-00			CAP., FXD, CER DI: 0.005UF, +80-20%, 150V	56289	19C242B
C1436	290-0782-00			CAP., FXD, ELCTLT: 4.7UF, +75-10%, 35V	56289	503D475G035AS
C1444	283-0067-00			CAP., FXD, CER DI: 0.001UF, 10%, 200V	72982	835-515B102K
C1445	281-0613-00			CAP., FXD, CER DI: 10PF, +/-1PF, 200V	72982	374-001C0G0100F
C1447	290-0778-00			CAP., FXD, ELCTLT: 1UF, +50-10%, 50V	0000L	ECE-A50N1

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff Dscont	Name & Description	Mfr Code	Mfr Part Number
C1454	283-0110-00		CAP., FXD, CER DI: 0.005UF, +80-20%, 150V	56289	19C242B
C1464	281-0540-00		CAP., FXD, CER DI: 51PF, 5%, 500V	72982	301-000U2J0510J
C1468	290-0420-00		CAP., FXD, ELCTLT: 0.68UF, 20%, 75V	56289	150D684X0075A2
C1469	283-0067-00		CAP., FXD, CER DI: 0.001UF, 10%, 200V	72982	835-515B102K
C1484	281-0629-00		CAP., FXD, CER DI: 33PF, 5%, 600V	72982	308-000C0G0330J
C1488	290-0420-00		CAP., FXD, ELCTLT: 0.68UF, 20%, 75V	56289	150D684X0075A2
C1514	281-0605-00		CAP., FXD, CER DI: 200PF, 10%, 500V	04222	7001-1375
C1556	290-0776-00		CAP., FXD, ELCTLT: 22UF, +50-10%, 10V	0000L	ECE-A10V22L
C1601	281-0547-00		CAP., FXD, CER DI: 2.7PF, 10%, 500V	72982	301-000C0J0279C
C1605	281-0773-00		CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1611	281-0547-00		CAP., FXD, CER DI: 2.7PF, 10%, 500V	72982	301-000C0J0279C
C1615	281-0773-00		CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1619	281-0562-00		CAP., FXD, CER DI: 39PF, 10%, 500V	72982	301-000U2J0390K
C1620	281-0092-00		CAP., VAR, CER DI: 9-35PF, 200V	72982	538-011 D9-35
C1623	281-0775-00		CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C1628	283-0271-00		CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1635	281-0158-00		CAP., VAR, CER DI: 7-45PF, 50V	73899	DVJ-5006
C1638	281-0773-00		CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1642	283-0000-00		CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1643	290-0745-00		CAP., FXD, ELCTLT: 22UF, +50-10%, 25V	56289	502D225
C1644	281-0775-00		CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C1646	290-0746-00		CAP., FXD, ELCTLT: 47UF, +50-10%, 16V	56289	502D226
C1645	290-0745-00		CAP., FXD, ELCTLT: 22UF, +50-10%, 25V	56289	502D225
C1651	281-0123-00		CAP., VAR, CER DI: 5-25PF, 100V	72982	518-000A5-25
C1653	281-0773-00		CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1656	281-0773-00		CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1660	281-0557-00		CAP., FXD, CER DI: 1.8PF, 10%, 500V	72982	301-000C0K0189B
C1663	281-0158-00		CAP., VAR, CER DI: 7-45PF, 50V	73899	DVJ-5006
C1664	281-0773-00		CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1665	281-0791-00		CAP., FXD, CER DI: 270PF, 10%, 100V	72982	8035D2AADX5R271K
C1671	281-0773-00		CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1672	283-0003-00		CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1675	281-0773-00		CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1676	281-0788-00		CAP., FXD, CER DI: 470PF, 10%, 100V	72982	8005H9AADW5R471K
C1677	283-0346-00		CAP., FXD, CER DI: 0.47UF, +80-20%, 100V	72982	8131-M100F474Z
C1680	283-0000-00		CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1681	283-0271-00		CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1687	283-0271-00		CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1692	281-0773-00		CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1694	283-0271-00		CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1698	290-0804-00		CAP., FXD, ELCTLT: 10UF, +50-10%, 25V	55680	503D106G025AS
C1707	290-0164-00		CAP., FXD, ELCTLT: 1UF, +50-10%, 150V	56289	30D105F150BA2
C1708	290-0164-00		CAP., FXD, ELCTLT: 1UF, +50-10%, 150V	56289	30D105F150BA2
C1710	283-0105-00		CAP., FXD, CER DI: 0.01UF, +80-20%, 2000V	56289	41C316
C1711	283-0105-00		CAP., FXD, CER DI: 0.01UF, +80-20%, 2000V	56289	41C316
C1712	283-0271-00		CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1714	283-0204-00		CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C1715	283-0003-00		CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1722	283-0023-00		CAP., FXD, CER DI: 0.01UF, +80-20%, 12V	71590	3DDU6BB104Z
C1724	283-0003-00		CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1734	283-0003-00		CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1735	281-0814-00		CAP., FXD, CER DI: 100PF, 10%, 100V	72982	8005D2AADCOG101K
C1736	285-0894-00		CAP., FXD, PLSTC: 5UF, 5%, 50V	56289	LP66A1A505J002

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C1747	283-0092-00			CAP., FXD, CER DI: 0.03UF, +80-20%, 200V	72982	845-534E303Z
C1749	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1750	283-0105-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 2000V	56289	41C316
C1752	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1754	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1755	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1756	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1764	283-0272-00			CAP., FXD, CER DI: 0.0068UF, 30%, 4000V	72982	3888-510C 682M
C1770	290-0767-00			CAP., FXD, ELCTLT: 4.7UF, +75-10%, 160V	56289	502D228
C1772	283-0010-00			CAP., FXD, CER DI: 0.05UF, +100-20%, 50V	56289	273C20
C1774	290-0767-00			CAP., FXD, ELCTLT: 4.7UF, +75-10%, 160V	56289	502D228
C1775	283-0177-00			CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N039 E 105Z
C1776	283-0177-00			CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N039 E 105Z
C1778	283-0006-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 500V	72982	084154525V00203Z
C1783	283-0108-00			CAP., FXD, CER DI: 220PF, 10%, 200V	56289	272C13
C1785	283-0032-00			CAP., FXD, CER DI: 470PF, 5%, 500V	72982	831-500Z5D471J
C1786	283-0272-00			CAP., FXD, CER DI: 0.0068UF, 30%, 4000V	72982	3888-510C 682M
C1791	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1792	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1793	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1797	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1803	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1807	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1818	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1819	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1820	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1821	283-0092-00			CAP., FXD, CER DI: 0.03UF, +80-20%, 200V	72982	845-534E303Z
C1831	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1834	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1839	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1842	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1846	283-0187-00			CAP., FXD, CER DI: 0.047UF, 10%, 400V	72982	8131N401X5R0473K
C1848	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1849	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1850	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1852	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1860	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1862	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1870	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1872	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1877	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1880	283-0271-00			CAP., FXD, CER DI: 0.001UF, 20%, 4000V	56289	33C325
C1890	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1893	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1901	281-0773-00			CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1904	281-0812-00			CAP., FXD, CER DI: 1000PF, 10%, 100V	72982	8005H9AADW5R102K
C1906	281-0812-00			CAP., FXD, CER DI: 1000PF, 10%, 100V	72982	8005H9AADW5R102K
C1908	290-0187-00			CAP., FXD, ELCTLT: 4.7UF, 20%, 35V	56289	150D475X0035B2
C1914	281-0763-00			CAP., FXD, CER DI: 47PF, 10%, 100V	72982	8035D9AADC1G470K
C1918	281-0812-00			CAP., FXD, CER DI: 1000PF, 10%, 100V	72982	8005H9AADW5R102K
C1919	281-0773-00			CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1920	281-0773-00			CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1921	281-0813-00			CAP., FXD, CER DI: 0.047UF, 20%, 100V	04222	GC705-E-473M

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C1935	281-0797-00			CAP., FXD, CER DI: 15PF, 10%, 100V	72982	8035D9AADCOG150K
C1938	281-0812-00			CAP., FXD, CER DI: 1000PF, 10%, 100V	72982	8005H9AADW5R102K
C1950	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C1952	281-0786-00			CAP., FXD, CER DI: 150PF, 10%, 100V	72982	8035D2AADX5P151K
C1953	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C1955	290-0536-00			CAP., FXD, ELCTLT: 10UF, 20%, 25V	90201	TDC106M025FL
C1956	290-0745-00			CAP., FXD, ELCTLT: 22UF, +50-10%, 25V	56289	502D225
C1968	290-0534-00			CAP., FXD, ELCTLT: 1UF, 20%, 35V	56289	196D105X0035HA1
C1969	281-0773-00			CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1971	285-0913-00			CAP., FXD, PLSTC: 3UF, 5%, 50V	84411	TEK34-3055R5
C1982	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C1984	281-0773-00			CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	8005H9AADW5R103K
C1985	290-0574-00			CAP., FXD, ELCTLT: 47UF, 10%, 20V	90201	TDC476K020CL
C1990	290-0745-00			CAP., FXD, ELCTLT: 22UF, +50-10%, 25V	56289	502D225
C1993	281-0812-00			CAP., FXD, CER DI: 1000PF, 10%, 100V	72982	8005H9AADW5R102K
C1994	281-0775-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8005D9AABZ5U104M
C1995	290-0804-00			CAP., FXD, ELCTLT: 10UF, +50-10%, 25V	55680	503D106G025AS
C1996	290-0804-00			CAP., FXD, ELCTLT: 10UF, +50-10%, 25V	55680	503D106G025AS
C1997	290-0804-00			CAP., FXD, ELCTLT: 10UF, +50-10%, 25V	55680	503D106G025AS
C2101	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2109	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C2112	283-0077-00			CAP., FXD, CER DI: 330PF, 5%, 500V	56289	40C94A3
C2115	290-0534-00			CAP., FXD, ELCTLT: 1UF, 20%, 35V	56289	196D105X0035HA1
C2117	290-0534-00			CAP., FXD, ELCTLT: 1UF, 20%, 35V	56289	196D105X0035HA1
C2119	290-0534-00			CAP., FXD, ELCTLT: 1UF, 20%, 35V	56289	196D105X0035HA1
C2121	283-0594-00			CAP., FXD, MICA D: 0.001UF, 1%, 100V	00853	D151F102F0
C2135	285-0698-00			CAP., FXD, PLSTC: 0.0082UF, 5%, 100V	56289	410P82251
C2140	283-0103-00			CAP., FXD, CER DI: 180PF, 5%, 500V	56289	40C638
C2144	281-0544-00			CAP., FXD, CER DI: 5.6PF, 10%, 500V	72982	301-000C0H0569D
C2145	290-0534-00			CAP., FXD, ELCTLT: 1UF, 20%, 35V	56289	196D105X0035HA1
C2155	283-0103-00			CAP., FXD, CER DI: 180PF, 5%, 500V	56289	40C638
C2183	283-0032-00			CAP., FXD, CER DI: 470PF, 5%, 500V	72982	831-500Z5D471J
C2185	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2214	283-0032-00			CAP., FXD, CER DI: 470PF, 5%, 500V	72982	831-500Z5D471J
C2242	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C2244	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2255	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C2281	283-0054-00			CAP., FXD, CER DI: 150PF, 5%, 200V	72982	855-535U2J151J
C4301	283-0177-00			CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N039 E 105Z
C4302	283-0177-00			CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N039 E 105Z
C4303	283-0177-00			CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N039 E 105Z
C4305	290-0755-00			CAP., FXD, ELCTLT: 100UF, +50-10%, 10V	56289	502D223
C4304	283-0177-00			CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N039 E 105Z
C4314	283-0672-00			CAP., FXD, MICA D: 200PF, 1%, 500V	00853	D155F201F0
C4315	281-0603-00			CAP., FXD, CER DI: 39PF, 5%, 500V	72982	308-000C0G0390J
C4316	283-0177-00			CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N039 E 105Z
C4335	281-0603-00			CAP., FXD, CER DI: 39PF, 5%, 500V	72982	308-000C0G0390J
C4336	281-0549-00			CAP., FXD, CER DI: 68PF, 10%, 500V	72982	301-000U2J0680K
C4342	283-0032-00			CAP., FXD, CER DI: 470PF, 5%, 500V	72982	831-500Z5D471J
C4343	281-0782-00			CAP., FXD, CER DI: 33PF, 10%, 500V	72982	301-000N4700330K
C4345	281-0782-00			CAP., FXD, CER DI: 33PF, 10%, 500V	72982	301-000N4700330K
C4346	283-0032-00			CAP., FXD, CER DI: 470PF, 5%, 500V	72982	831-500Z5D471J
C4347	283-0638-00			CAP., FXD, MICA D: 130PF, 1%, 100V	00853	D151F131F0

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C4423	281-0603-00			CAP., FXD, CER DI: 39PF, 5%, 500V	72982	308-000C0G0390J
C4441	281-0603-00			CAP., FXD, CER DI: 39PF, 5%, 500V	72982	308-000C0G0390J
C4449	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C4461	281-0589-00			CAP., FXD, CER DI: 170PF, 5%, 500V	72982	301000Z5D0171J
C4467	281-0589-00			CAP., FXD, CER DI: 170PF, 5%, 500V	72982	301000Z5D0171J
C4470	283-0111-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8121-N088Z5U104M
C4475	283-0177-00			CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N039 E 105Z
C4483	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C4484	283-0177-00			CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N039 E 105Z
C4485	283-0060-00			CAP., FXD, CER DI: 100PF, 5%, 200V	72982	855-535U2J101J
CR52	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR71	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR81	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR82	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR83	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR86	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR88	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR342	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR362	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR386	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR552	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR651	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR654	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR711	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR712	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR767	152-0322-00			SEMICONV DEVICE: SILICON, 15V, HOT CARRIER	28480	5082-2672
CR777	152-0322-00			SEMICONV DEVICE: SILICON, 15V, HOT CARRIER	28480	5082-2672
CR862	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR863	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR864	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR875	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR878	152-0066-00			SEMICONV DEVICE: SILICON, 400V, 750MA	80009	152-0066-00
CR883	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR886	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR891	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR893	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR897	152-0066-00			SEMICONV DEVICE: SILICON, 400V, 750MA	80009	152-0066-00
CR1006	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1082	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1112	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1112	-----			* OPTION 2 ONLY		
CR1215	152-0396-01			SEMICONV DEVICE: SILICON, 400V, 3A	12969	652-821
CR1232	152-0107-00			SEMICONV DEVICE: SILICON, 400V, 400MA	80009	152-0107-00
CR1234	152-0400-00			SEMICONV DEVICE: SILICON, 400V, 1A	80009	152-0400-00
CR1236	152-0061-00			SEMICONV DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR1237	152-0061-00			SEMICONV DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR1240	152-0107-00			SEMICONV DEVICE: SILICON, 400V, 400MA	80009	152-0107-00
CR1241	152-0400-00			SEMICONV DEVICE: SILICON, 400V, 1A	80009	152-0400-00
CR1244	152-0107-00			SEMICONV DEVICE: SILICON, 400V, 400MA	80009	152-0107-00
CR1245	152-0061-00			SEMICONV DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR1249	152-0107-00			SEMICONV DEVICE: SILICON, 400V, 400MA	80009	152-0107-00
CR1252	152-0333-00			SEMICONV DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
CR1259	152-0333-00			SEMICONV DEVICE: SILICON, 55V, 200MA	80009	152-0333-00

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
CR1265	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1266	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1273	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1274	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1275	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1276	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1281	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1282	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1283	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1284	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1290	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1320	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1321	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1322	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1323	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1324	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1325	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1327	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1330	152-0586-00			SEMICON D DEVICE:SILICON,600V,500MA	14936	RGP10J
CR1331	152-0586-00			SEMICON D DEVICE:SILICON,600V,500MA	14936	RGP10J
CR1332	152-0586-00			SEMICON D DEVICE:SILICON,600V,500MA	14936	RGP10J
CR1333	152-0586-00			SEMICON D DEVICE:SILICON,600V,500MA	14936	RGP10J
CR1340	152-0397-00			SEMICON D DEVICE:SILICON,50V,12A	80009	152-0397-00
CR1341	152-0397-00			SEMICON D DEVICE:SILICON,50V,12A	80009	152-0397-00
CR1342	152-0397-00			SEMICON D DEVICE:SILICON,50V,12A	80009	152-0397-00
CR1343	152-0397-00			SEMICON D DEVICE:SILICON,50V,12A	80009	152-0397-00
CR1350	152-0586-00			SEMICON D DEVICE:SILICON,600V,500MA	14936	RGP10J
CR1351	152-0692-00			SEMICON D DEVICE:SILICON,20V,30A	80009	152-0692-00
CR1353	152-0586-00			SEMICON D DEVICE:SILICON,600V,500MA	14936	RGP10J
CR1361	152-0008-00			SEMICON D DEVICE:GERMANIUM,75V,60MA	80009	152-0008-00
CR1371	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1372	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1374	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1407	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1408	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1410	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1411	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1415	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1419	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1420	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1421	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1422	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1428	152-0066-00			SEMICON D DEVICE:SILICON,400V,750MA	80009	152-0066-00
CR1445	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1449	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1450	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1452	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1453	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1458	152-0066-00			SEMICON D DEVICE:SILICON,400V,750MA	80009	152-0066-00
CR1464	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1476	152-0066-00			SEMICON D DEVICE:SILICON,400V,750MA	80009	152-0066-00
CR1484	152-0333-00			SEMICON D DEVICE:SILICON,55V,200MA	80009	152-0333-00
CR1496	152-0066-00			SEMICON D DEVICE:SILICON,400V,750MA	80009	152-0066-00

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
CR1514	152-0333-00			SEMICON D DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
CR1532	152-0066-00			SEMICON D DEVICE: SILICON, 400V, 750MA	80009	152-0066-00
CR1542	152-0423-00			SEMICON D DEVICE: SILICON, 400V, 3A	04713	1N5000
CR1543	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1544	152-0423-00			SEMICON D DEVICE: SILICON, 400V, 3A	04713	1N5000
CR1548	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1600	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1607	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1608	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1609	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1618	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1623	152-0574-00			SEMICON D DEVICE: SILICON, 120V, 0.15A	80009	152-0574-00
CR1624	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1649	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1665	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1666	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1675	152-0574-00			SEMICON D DEVICE: SILICON, 120V, 0.15A	80009	152-0574-00
CR1676	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1677	152-0574-00			SEMICON D DEVICE: SILICON, 120V, 0.15A	80009	152-0574-00
CR1678	152-0574-00			SEMICON D DEVICE: SILICON, 120V, 0.15A	80009	152-0574-00
CR1687	152-0574-00			SEMICON D DEVICE: SILICON, 120V, 0.15A	80009	152-0574-00
CR1688	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1690	152-0107-00			SEMICON D DEVICE: SILICON, 400V, 400MA	80009	152-0107-00
CR1691	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1692	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1694	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1696	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1698	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1707	152-0107-00			SEMICON D DEVICE: SILICON, 400V, 400MA	80009	152-0107-00
CR1708	152-0107-00			SEMICON D DEVICE: SILICON, 400V, 400MA	80009	152-0107-00
CR1710	152-0429-00			SEMICON D DEVICE: SILICON, 5000V, 10MA	14099	SA3282
CR1711	152-0429-00			SEMICON D DEVICE: SILICON, 5000V, 10MA	14099	SA3282
CR1713	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1714	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1724	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1736	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1747	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1749	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1752	152-0409-00			SEMICON D DEVICE: SILICON, 12, 000V, 5MA	80009	152-0409-00
CR1753	152-0409-00			SEMICON D DEVICE: SILICON, 12, 000V, 5MA	80009	152-0409-00
CR1762	152-0409-00			SEMICON D DEVICE: SILICON, 12, 000V, 5MA	80009	152-0409-00
CR1763	152-0409-00			SEMICON D DEVICE: SILICON, 12, 000V, 5MA	80009	152-0409-00
CR1771	152-0586-00			SEMICON D DEVICE: SILICON, 600V, 500MA	14936	RGP10J
CR1772	152-0586-00			SEMICON D DEVICE: SILICON, 600V, 500MA	14936	RGP10J
CR1774	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1775	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1776	152-0586-00			SEMICON D DEVICE: SILICON, 600V, 500MA	14936	RGP10J
CR1778	152-0586-00			SEMICON D DEVICE: SILICON, 600V, 500MA	14936	RGP10J
CR1785	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1788	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1789	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR1792	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1794	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
CR1803	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1804	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1816	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1818	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1819	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1820	152-0242-00			SEMICON D DEVICE:SILICON,225V,200MA	80009	152-0242-00
CR1835	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1838	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1842	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1900	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1902	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1916	152-0322-00			SEMICON D DEVICE:SILICON,15V,HOT CARRIER	28480	5082-2672
CR1918	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1922	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1923	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1927	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1928	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1929	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1946	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1947	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1948	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1963	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1971	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1972	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1974	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1991	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1992	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1993	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1994	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR1998	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2009	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2019	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2124	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2125	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2127	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2140	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2141	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2142	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2145	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2146	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2156	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2157	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2162	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2163	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2166	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2167	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2170	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2171	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2174	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2175	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2192	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2193	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02
CR2196	152-0141-02			SEMICON D DEVICE:SILICON,30V,150MA	80009	152-0141-02

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
CR2198	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR2226	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR2235	152-0333-00			SEMICON D DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
THRU	-----					
CR2266	152-0333-00			SEMICON D DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
CR4322	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR4323	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4354	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4355	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4356	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4357	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4368	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4369	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4433	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4434	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4448	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4449	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4461	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4467	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4471	152-0153-00			SEMICON D DEVICE: SILICON, 15V, 50MA	80009	152-0153-00
CR4472	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4473	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4474	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4487	152-0075-00			SEMICON D DEVICE: GE, 25V, 40MA	80009	152-0075-00
CR4491	152-0075-00			SEMICON D DEVICE: GE, 25V, 40MA	80009	152-0075-00
CR4492	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4493	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4494	152-0025-00			SEMICON D DEVICE: GE, 125V, 100MA	14936	1M634
CR4495	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4496	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4498	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 150MA	80009	152-0141-02
CR4499	152-0025-00			SEMICON D DEVICE: GE, 125V, 100MA	14936	1M634
DL592	119-0933-00			DELAY, LINE, ELEC: 52NH, 50 OHM	80009	119-0933-00
DL1165	119-0932-00			DELAY, LINE, ELEC: 47NS, 100 OHM	80009	119-0932-00
DL1165	-----			* OPTION 2 ONLY		
DS304	150-0029-00			LAMP, INCAND: 6.3V, 0.20A	08806	349
DS305	150-0029-00			LAMP, INCAND: 6.3V, 0.20A	08806	349
DS306	150-0029-00			LAMP, INCAND: 6.3V, 0.20A	08806	349
DS308	150-0121-02			LAMP, CARTRIDGE: GREEN, 5V, 60MA	80009	150-0121-02
DS342	150-0093-01			LAMP, INCAND: 5V, 0.06A, 0.05MSCP, SEL	87034	9AS15
DS345	150-0093-01			LAMP, INCAND: 5V, 0.06A, 0.05MSCP, SEL	87034	9AS15
DS346	150-0093-01			LAMP, INCAND: 5V, 0.06A, 0.05MSCP, SEL	87034	9AS15
DS362	150-0093-01			LAMP, INCAND: 5V, 0.06A, 0.05MSCP, SEL	87034	9AS15
DS365	150-0093-01			LAMP, INCAND: 5V, 0.06A, 0.05MSCP, SEL	87034	9AS15
DS366	150-0093-01			LAMP, INCAND: 5V, 0.06A, 0.05MSCP, SEL	87034	9AS15
DS1219	150-0035-00			LAMP, GLOW: 90V, 0.3MA	53944	A1B-3
DS1682	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1792	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1794	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1818	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1819	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
DS1820	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1842	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1844	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1846	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1848	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1970	150-1033-00			LAMP, LED: YELLOW, 2.2V	50434	5082-4584
DS1994	150-1031-00			LAMP, LED: RED, 650NM, 40MA MAX	53184	XC209R
DS2002	150-0048-01			LAMP, INCAND: 5V, 0.06A, SEL	08806	683AS15
DS2003	150-0048-01			LAMP, INCAND: 5V, 0.06A, SEL	08806	683AS15
E1208	119-0181-00			SURGE VOLTAGE P: 230VAC, +/-15%	80009	119-0181-00
E1213	119-0181-00			SURGE VOLTAGE P: 230VAC, +/-15%	80009	119-0181-00
F1200	159-0017-00			FUSE, CARTRIDGE: 3AG, 4A, 250V, FAST BLOW	71400	MTH4
FL1200	119-0420-00			FILTER, RFI: 6A, 250VAC, 400HZ	02777	F-11935-6
K1112	148-0071-00			RELAY, ARMATURE: PLUG-IN, DPDT	99699	2X-A1538
K1112	-----			* OPTION 2 ONLY		
K1162	148-0071-00			RELAY, ARMATURE: PLUG-IN, DPDT	99699	2X-A1538
K1162	-----			* OPTION 2 ONLY		
L236	108-0734-00			COIL, RF: 160NH	80009	108-0734-00
L238	108-0734-00			COIL, RF: 160NH	80009	108-0734-00
L246	108-0734-00			COIL, RF: 160NH	80009	108-0734-00
L248	108-0734-00			COIL, RF: 160NH	80009	108-0734-00
L387	108-0440-00			COIL, RF: 8UH, TOROIDAL INDUCTOR	80009	108-0440-00
L436	108-0734-00			COIL, RF: 160NH	80009	108-0734-00
L438	108-0734-00			COIL, RF: 160NH	80009	108-0734-00
L446	108-0734-00			COIL, RF: 160NH	80009	108-0734-00
L448	108-0734-00			COIL, RF: 160NH	80009	108-0734-00
L480	108-0324-00			COIL, RF: 10MH	76493	70F102A1
L486	108-0733-00			COIL, RF: 113NH	80009	108-0733-00
L582	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L583	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L584	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L762	108-0620-00			COIL, RF: 90NH	80009	108-0620-00
L763	108-0371-00			COIL, RF: 0.23UH	80009	108-0371-00
L764	108-0057-00			COIL, RF: 8.8UH	80009	108-0057-00
L772	108-0620-00			COIL, RF: 90NH	80009	108-0620-00
L773	108-0371-00			COIL, RF: 0.23UH	80009	108-0371-00
L774	108-0057-00			COIL, RF: 8.8UH	80009	108-0057-00
L857	108-0683-00			COIL, RF: 900MH	80009	108-0683-00
L891	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L893	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L895	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L897	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L1001	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L1002	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L1003	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L1004	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L1042	108-0733-00			COIL, RF: 113NH	80009	108-0733-00
L1062	108-0733-00			COIL, RF: 113NH	80009	108-0733-00
L1156	108-0606-00			COIL, RF: 50NH	80009	108-0606-00
L1156	-----			* OPTION 2 ONLY		
L1229	108-0681-00			COIL, RF: 140UH	80009	108-0681-00

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
L1237	108-0761-00			COIL, RF: 1MH	80009	108-0761-00
L1332	108-0473-00			COIL, RF: 150UH	80009	108-0473-00
L1334	108-0473-00			COIL, RF: 150UH	80009	108-0473-00
L1342	108-0680-00			COIL, RF: 27UH	80009	108-0680-00
L1344	108-0680-00			COIL, RF: 27UH	80009	108-0680-00
L1352	108-0473-00			COIL, RF: 150UH	80009	108-0473-00
L1354	108-0556-00			COIL, RF: 12UH	80009	108-0556-00
L1356	108-0337-00			COIL, RF: 25UH	80009	108-0337-00
L1627	108-0215-00			COIL, RF: 1.1UH	80009	108-0215-00
L1643	108-0543-00			COIL, RF: FIXED, 1.1UH	80009	108-0543-00
L1645	108-0543-00			COIL, RF: FIXED, 1.1UH	80009	108-0543-00
L1995	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L1996	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L1997	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L2283	108-0331-00			COIL, RF: 0.75UH	80009	108-0331-00
L4301	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L4302	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L4303	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L4304	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L4317	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L4342	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L4344	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
LR857	108-0683-00			COIL, RF: 900MH	80009	108-0683-00
LR885	108-0543-00			COIL, RF: FIXED, 1.1UH	80009	108-0543-00
LR1096	108-0325-00			COIL, RF: 490NH	80009	108-0325-00
LR1097	108-0685-00			COIL, RF: 62NH	80009	108-0685-00
LR1098	108-0685-00			COIL, RF: 62NH	80009	108-0685-00
LR1142	108-0729-00			COIL, RF: 195NH	80009	108-0729-00
LR1142	-----			* OPTION 2 ONLY		
LR1644	108-0537-00			COIL, RF: 200UH	80009	108-0537-00
LR4338	108-0543-00			COIL, RF: FIXED, 1.1UH	80009	108-0543-00
LR4359	108-0543-00			COIL, RF: FIXED, 1.1UH	80009	108-0543-00
LR4368	108-0543-00			COIL, RF: FIXED, 1.1UH	80009	108-0543-00
LR4412	108-0543-00			COIL, RF: FIXED, 1.1UH	80009	108-0543-00
Q75	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q254	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q342	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q346	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q362	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q366	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q376	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q382	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q384	151-0342-00			TRANSISTOR: SILICON, PNP	80009	151-0342-00
Q454	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q542	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q548	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q556	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q558	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q656	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q642	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q648	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q652	151-0301-00			TRANSISTOR: SILICON, PNP	04713	2N2907A

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
Q658	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q672	151-0301-00			TRANSISTOR: SILICON, PNP	04713	2N2907A
Q676	151-0235-00			TRANSISTOR: SILICON, PNP	80009	151-0235-00
Q682	151-0301-00			TRANSISTOR: SILICON, PNP	04713	2N2907A
Q712	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q718	151-0301-00			TRANSISTOR: SILICON, PNP	04713	2N2907A
Q722	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q732	151-0333-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS918	80009	151-0333-00
Q742	151-0216-00			TRANSISTOR: SILICON, NPN	80009	151-0216-00
Q748	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q752	151-0216-00			TRANSISTOR: SILICON, PNP	80009	151-0216-00
Q758	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q814	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q824	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q862	151-0183-00			TRANSISTOR: SILICON, NPN	80009	151-0183-00
Q864	151-0301-00			TRANSISTOR: SILICON, PNP	04713	2N2907A
Q872	151-0301-00			TRANSISTOR: SILICON, PNP	04713	2N2907A
Q873	151-0529-00			TRANSISTOR: SCR, 200V, 0.5A	04713	MCR206
Q878	151-0136-00			TRANSISTOR: SILICON, NPN	02735	35495
Q884	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q892	151-0136-00			TRANSISTOR: SILICON, NPN	02735	35495
Q914	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q923	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q924A-E	156-0048-00			MICROCIRCUIT, LI: FIVE NPN TRANSISTOR ARRAY	80009	156-0048-00
Q962	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q964	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q992	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q994	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q1022	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q1024	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q1028	151-0424-00			TRANSISTOR: SILICON, NPN	80009	151-0424-00
Q1034	151-0424-00			TRANSISTOR: SILICON, NPN	80009	151-0424-00
Q1046	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1049	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1052	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1058	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q1066	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1072	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1078	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q1084	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q1166	151-0301-00			TRANSISTOR: SILICON, PNP	04713	2N2907A
Q1166	-----			* OPTION 2 ONLY		
Q1234	151-0632-00			TRANSISTOR: SILICON, NPN	80009	151-0632-00
Q1238	151-0508-00			TRANSISTOR: SILICON, NPN, PROGRAMMABLE	03508	2N6027
Q1240	151-0632-00			TRANSISTOR: SILICON, NPN	80009	151-0632-00
Q1243	151-0347-00			TRANSISTOR: SILICON, NPN	80009	151-0347-00
Q1245	151-0350-00			TRANSISTOR: SILICON, PNP	80009	151-0350-00
Q1246	151-0260-00			TRANSISTOR: SILICON, NPN	80009	151-0260-00
Q1252	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q1254	151-0273-00			TRANSISTOR: SILICON, NPN	80009	151-0273-00
Q1362	151-0190-00			TRANSISTOR: SILICON, NPN	80009	151-0190-00
Q1422	151-0350-00			TRANSISTOR: SILICON, PNP	80009	151-0350-00
Q1428	151-0656-00			TRANSISTOR: SILICON, NPN	04713	SJE1972

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
Q1434	151-0103-00			TRANSISTOR: SILICON, NPN	80009	151-0103-00
Q1438	151-0134-00			TRANSISTOR: SILICON, PNP	80009	151-0134-00
Q1452	151-0347-00			TRANSISTOR: SILICON, NPN	80009	151-0347-00
Q1458	151-0657-00			TRANSISTOR: SILICON, PNP	04713	SJE1973
Q1468	151-0347-00			TRANSISTOR: SILICON, NPN	80009	151-0347-00
Q1474	151-0656-00			TRANSISTOR: SILICON, NPN	04713	SJE1972
Q1488	151-0342-00			TRANSISTOR: SILICON, PNP	80009	151-0342-00
Q1494	151-0657-00			TRANSISTOR: SILICON, PNP	04713	JE1973
Q1518	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q1522	151-0349-00			TRANSISTOR: SILICON, NPN, SEL FROM MJE2801	80009	151-0349-00
Q1526	151-0477-00			TRANSISTOR: SILICON, NPN	01295	TIP35A
Q1544	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q1548	151-0373-00			TRANSISTOR: SILICON, PNP	80009	151-0373-00
Q1603	151-0438-00			TRANSISTOR: SILICON, PNP, SEL FROM SPS6927	80009	151-0438-00
Q1607	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q1608	151-0438-00			TRANSISTOR: SILICON, PNP, SEL FROM SPS6927	80009	151-0438-00
Q1617	151-0472-00			TRANSISTOR: SILICON, NPN	80009	151-0472-00
Q1618	151-0438-00			TRANSISTOR: SILICON, PNP, SEL FROM SPS6927	80009	151-0438-00
Q1620	151-0472-00			TRANSISTOR: SILICON, NPN	80009	151-0472-00
Q1626	151-0427-00			TRANSISTOR: SILICON, NPN	80009	151-0427-00
Q1629	151-0438-00			TRANSISTOR: SILICON, PNP, SEL FROM SPS6927	80009	151-0438-00
Q1632	151-0438-00			TRANSISTOR: SILICON, PNP, SEL FROM SPS6927	80009	151-0438-00
Q1644	151-0190-00			TRANSISTOR: SILICON, NPN	80009	151-0190-00
Q1648	151-0438-00			TRANSISTOR: SILICON, PNP, SEL FROM SPS6927	80009	151-0438-00
Q1652	151-0472-00			TRANSISTOR: SILICON, NPN	80009	151-0472-00
Q1658	151-0438-00			TRANSISTOR: SILICON, PNP, SEL FROM SPS6927	80009	151-0438-00
Q1664	151-0438-00			TRANSISTOR: SILICON, PNP, SEL FROM SPS6927	80009	151-0438-00
Q1666	151-0190-00			TRANSISTOR: SILICON, NPN	80009	151-0190-00
Q1668	151-0659-00			TRANSISTOR: SILICON, NPN	80009	151-0659-00
Q1672	151-0301-00			TRANSISTOR: SILICON, PNP	04713	2N2907A
Q1676	151-0659-00			TRANSISTOR: SILICON, NPN	80009	151-0659-00
Q1687	151-0444-00			TRANSISTOR: SILICON, NPN	80009	151-0444-00
Q1690	156-0281-00			MICROCIRCUIT, LI: 4 TRANSISTOR ARRAY	80009	156-0281-00
Q1698	151-0342-00			TRANSISTOR: SILICON, PNP	80009	151-0342-00
Q1708	151-0150-00			TRANSISTOR: SILICON, NPN	80009	151-0150-00
Q1724	151-0453-00			TRANSISTOR: SILICON, PNP	80009	151-0453-00
Q1742	151-0350-00			TRANSISTOR: SILICON, PNP	80009	151-0350-00
Q1748	151-0350-00			TRANSISTOR: SILICON, PNP	80009	151-0350-00
Q1784	151-0279-00			TRANSISTOR: SILICON, NPN	80009	151-0279-00
Q1835	151-0126-00			TRANSISTOR: SILICON, NPN	80009	151-0126-00
Q1838	151-0126-00			TRANSISTOR: SILICON, NPN	80009	151-0126-00
Q1842	151-0350-00			TRANSISTOR: SILICON, PNP	80009	151-0350-00
Q1908	151-0508-00			TRANSISTOR: SILICON, NPN, PROGRAMMABLE	03508	2N6027
Q1910	151-0341-00			TRANSISTOR: SILICON, NPN	80009	151-0341-00
Q1916	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q1928	151-0271-00			TRANSISTOR: SILICON, PNP	80009	151-0271-00
Q1934	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q1938	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q1942	151-0301-00			TRANSISTOR: SILICON, PNP	04713	2N2907A
Q1943	151-0198-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS918	80009	151-0198-00
Q1946	151-0198-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS918	80009	151-0198-00
Q1956	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q1970	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
Q1974	151-1021-00			TRANSISTOR: SILICON, JFE	80009	151-1021-00
Q1978	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q1980	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q1982	151-0301-00			TRANSISTOR: SILICON, PNP	04713	2N2907A
Q1994	151-0301-00			TRANSISTOR: SILICON, PNP	04713	2N2907A
Q1995	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q1998	151-0188-00			TRANSISTOR: SILICON, PNP	80009	151-0188-00
Q1999	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q2108	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q2112	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q2138	151-0188-00			TRANSISTOR: SILICON, PNP	80009	151-0188-00
Q2153	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q2159	151-0190-00			TRANSISTOR: SILICON, NPN	80009	151-0190-00
Q2215	151-0232-00			TRANSISTOR: SILICON, NPN, DUAL	80009	151-0232-00
Q2223	151-0190-00			TRANSISTOR: SILICON, NPN	80009	151-0190-00
Q2225	151-0188-00			TRANSISTOR: SILICON, PNP	80009	151-0188-00
Q2229	151-0190-00			TRANSISTOR: SILICON, NPN	80009	151-0190-00
Q2240	151-0190-00			TRANSISTOR: SILICON, NPN	80009	151-0190-00
Q2286	151-0188-00			TRANSISTOR: SILICON, PNP	80009	151-0188-00
Q2287	151-0188-00			TRANSISTOR: SILICON, PNP	80009	151-0188-00
Q2296	151-0188-00			TRANSISTOR: SILICON, PNP	80009	151-0188-00
Q2299	151-0188-00			TRANSISTOR: SILICON, NPN	80009	151-0188-00
Q4336	151-0198-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS918	80009	151-0198-00
Q4364	151-0198-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS918	80009	151-0198-00
Q4374	151-0188-00			TRANSISTOR: SILICON, PNP	80009	151-0188-00
Q4382	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q4392	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q4424	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q4432	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q4438	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q4442	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q4448	151-0216-00			TRANSISTOR: SILICON, PNP	80009	151-0216-00
Q4456	151-1022-00			TRANSISTOR: SILICON, JFE, SEL FROM 2N4392	80009	151-1022-00
Q4462	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q4468	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q4480	151-0188-00			TRANSISTOR: SILICON, PNP	80009	151-0188-00
Q4488	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q4492	151-0188-00			TRANSISTOR: SILICON, PNP	80009	151-0188-00
Q4494	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q4498	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q4508	156-0048-00			MICROCIRCUIT, LI: FIVE NPN TRANSISTOR ARRAY	80009	156-0048-00
R20	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R22	321-0260-00			RES., FXD, FILM: 4.99K OHM, 1%, 0.125W	91637	MFF1816G49900F
R23	321-0260-00			RES., FXD, FILM: 4.99K OHM, 1%, 0.125W	91637	MFF1816G49900F
R40	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R42	321-0260-00			RES., FXD, FILM: 4.99K OHM, 1%, 0.125W	91637	MFF1816G49900F
R43	321-0260-00			RES., FXD, FILM: 4.99K OHM, 1%, 0.125W	91637	MFF1816G49900F
R52	315-0472-00			RES., FXD, CMPSN: 4.7K OHM, 5%, 0.25W	01121	CB4725
R60	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R61	317-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R62	317-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R66	315-0302-00			RES., FXD, CMPSN: 3K OHM, 5%, 0.25W	01121	CB3025

Ckt No.	Tektronix Part No.	Serial/Model No. Eff Dscont	Name & Description	Mfr Code	Mfr Part Number
R67	315-0202-00		RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R71	315-0202-00		RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R74	315-0202-00		RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R75	315-0102-00		RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R80	315-0470-00		RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R81	317-0510-00		RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R82	317-0510-00		RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R83	315-0243-00		RES., FXD, CMPSN: 24K OHM, 5%, 0.25W	01121	CB2435
R85	315-0105-00		RES., FXD, CMPSN: 1M OHM, 5%, 0.25W	01121	CB1055
R86	315-0152-00		RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R87	315-0103-00		RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R88	315-0152-00		RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R90	315-0202-00		RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R91	315-0132-00		RES., FXD, CMPSN: 1.3K OHM, 5%, 0.25W	01121	CB1325
R92	315-0470-00		RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R93	321-0231-00		RES., FXD, FILM: 2.49K OHM, 1%, 0.125W	91637	MFF1816G24900F
R94	323-0160-00		RES., FXD, FILM: 453 OHM, 1%, 0.50W	75042	CECT0-4530F
R95	321-0231-00		RES., FXD, FILM: 2.49K OHM, 1%, 0.125W	91637	MFF1816G24900F
R97	315-0132-00		RES., FXD, CMPSN: 1.3K OHM, 5%, 0.25W	01121	CB1325
R99	315-0132-00		RES., FXD, CMPSN: 1.3K OHM, 5%, 0.25W	01121	CB1325
R201	321-0164-00		RES., FXD, FILM: 499 OHM, 1%, 0.125W	91637	MFF1816G499ROF
R202	321-0164-00		RES., FXD, FILM: 499 OHM, 1%, 0.125W	91637	MFF1816G499ROF
R205	315-0103-00		RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R208	321-0164-00		RES., FXD, FILM: 499 OHM, 1%, 0.125W	91637	MFF1816G499ROF
R209	321-0164-00		RES., FXD, FILM: 499 OHM, 1%, 0.125W	91637	MFF1816G499ROF
R212	325-0053-00		RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R213	325-0053-00		RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R214	325-0053-00		RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R216	325-0053-00		RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R217	325-0053-00		RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R218	325-0053-00		RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R232	321-0202-00		RES., FXD, FILM: 1.24K OHM, 1%, 0.125W	91637	MFF1816G12400F
R233	322-0111-00		RES., FXD, FILM: 140 OHM, 1%, 0.25W	91637	MFF1421G140ROF
R234	322-0170-00		RES., FXD, FILM: 576 OHM, 1%, 0.25W	75042	CEBT0-5760F
R235	315-0202-00		RES., FXD, FILM: 1.24K OHM, 1%, 0.125W	91637	MFF1816G12400F
R236	321-0147-00		RES., FXD, FILM: 332 OHM, 1%, 0.125W	91637	MFF1816G332ROF
R237	315-0103-00		RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R238	321-0155-00		RES., FXD, FILM: 402 OHM, 1%, 0.125W	91637	MFF1816G402ROF
R239	321-0085-00		RES., FXD, FILM: 75 OHM, 1%, 0.125W	91637	MFF1816G75R00F
R240	315-0100-00		RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R241	322-0114-00		RES., FXD, FILM: 150 OHM, 1%, 0.25W	75042	CEBT0-1500F
R242	321-0202-00		RES., FXD, FILM: 1.24K OHM, 1%, 0.125W	91637	MFF1816G12400F
R243	322-0111-00		RES., FXD, FILM: 140 OHM, 1%, 0.25W	91637	MFF1421G140ROF
R244	322-0170-00		RES., FXD, FILM: 576 OHM, 1%, 0.25W	75042	CEBT0-5760F
R245	321-0202-00		RES., FXD, FILM: 1.24K OHM, 1%, 0.125W	91637	MFF1816G12400F
R246	321-0147-00		RES., FXD, FILM: 332 OHM, 1%, 0.125W	91637	MFF1816G332ROF
R247	315-0103-00		RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R248	321-0155-00		RES., FXD, FILM: 402 OHM, 1%, 0.125W	91637	MFF1816G402ROF
R250	317-0200-00		RES., FXD, CMPSN: 20 OHM, 5%, 0.125W	01121	BB2005
R251	321-0218-00		RES., FXD, FILM: 1.82K OHM, 1%, 0.125W	91637	MFF1816G18200F
R252	321-0242-00		RES., FXD, FILM: 3.24K OHM, 1%, 0.125W	91637	MFF1816G32400F
R254	315-0102-00		RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R255	311-1236-00		RES., VAR, NONWIR: 250 OHM, 10%, 0.50W	73138	72X-22-0-251K

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R256	321-0062-00			RES., FXD, FILM: 43.2 OHM, 1%, 0.125W	91637	MFF1816G43R20F
R261	321-0178-00			RES., FXD, FILM: 698 OHM, 1%, 0.125W	91637	MFF1816G698R0F
R262	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R263	322-0151-00			RES., FXD, FILM: 365 OHM, 1%, 0.25W	75042	CEBTO-3650F
R264	321-0201-00			RES., FXD, FILM: 1.21K OHM, 1%, 0.125W	91637	MFF1816G12100F
R265	321-0285-00			RES., FXD, FILM: 9.09K OHM, 1%, 0.125W	91637	MFF1816G90900F
R270	311-1239-00			RES., VAR, NONWIR: 2.5K OHM, 10%, 0.5W	73138	72X-76-252K
R271	321-0178-00			RES., FXD, FILM: 698 OHM, 1%, 0.125W	91637	MFF1816G698R0F
R272	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R273	322-0239-00			RES., FXD, FILM: 3.01K OHM, 1%, 0.25W	75042	CEBTO-3011F
R274	311-1248-00			RES., VAR, NONWIR: 500 OHM, 10%, 0.50W	73138	72X-23-0-501K
R277	317-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R278	322-0085-00			RES., FXD, FILM: 75 OHM, 1%, 0.25W	75042	CEBTO-75R00F
R279	311-1936-00			RES., VAR, NONWIR: 50 OHM, 20%, 0.5W	73138	MODEL 72X
R280	317-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R301	303-0301-00			RES., FXD, CMPSN: 300 OHM, 5%, 1W	01121	GB3015
R324	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R325	311-1373-00			RES., VAR, NONWIR: 5K OHM, 20%, 1W	01121	16M188
R326	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R341	307-0109-00			RES., FXD, CMPSN: 8.2 OHM, 5%, 0.25W	01121	CB82G5
R342	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R343	315-0162-00			RES., FXD, CMPSN: 1.6K OHM, 5%, 0.25W	01121	CB1625
R345	307-0109-00			RES., FXD, CMPSN: 8.2 OHM, 5%, 0.25W	01121	CB82G5
R346	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R347	307-0109-00			RES., FXD, CMPSN: 8.2 OHM, 5%, 0.25W	01121	CB82G5
R361	307-0109-00			RES., FXD, CMPSN: 8.2 OHM, 5%, 0.25W	01121	CB82G5
R362	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R363	315-0162-00			RES., FXD, CMPSN: 1.6K OHM, 5%, 0.25W	01121	CB1625
R365	307-0109-00			RES., FXD, CMPSN: 8.2 OHM, 5%, 0.25W	01121	CB82G5
R366	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R367	307-0109-00			RES., FXD, CMPSN: 8.2 OHM, 5%, 0.25W	01121	CB82G5
R368	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R372	315-0823-00			RES., FXD, CMPSN: 82K OHM, 5%, 0.25W	01121	CB8235
R373	321-0258-00			RES., FXD, FILM: 4.75K OHM, 1%, 0.125W	91637	MFF1816G47500F
R374	321-0822-06			RES., FXD, FILM: 1.76K OHM, 0.25%, 0.125W	91637	MFF1816C17600C
R375	311-1566-00			RES., VAR, NONWIR: 200 OHM, 20%, 0.50W	73138	91-88-0
R376	321-0321-07			RES., FXD, FILM: 21.5K OHM, 0.1%, 0.125W	91637	MFF1816C21501B
R380	315-0362-00			RES., FXD, CMPSN: 3.6K OHM, 5%, 0.25W	01121	CB3625
R381	321-0321-07			RES., FXD, FILM: 21.5K OHM, 0.1%, 0.125W	91637	MFF1816C21501B
R382	315-0223-00			RES., FXD, CMPSN: 22K OHM, 5%, 0.25W	01121	CB2235
R383	321-0166-00			RES., FXD, FILM: 523 OHM, 1%, 0.125W	91637	MFF1816G523R0F
R384	308-0307-00			RES., FXD, WW: 5K OHM, 1%, 3W	91637	RS2B-B50000F
R385	311-1225-00			RES., VAR, NONWIR: 1K OHM, 20%, 0.50W	32997	3386F-T04-102
R386	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R387	321-1611-07			RES., FXD, FILM: 550 OHM, 0.1%, 0.125W	91637	MFF1816C550R0B
R392	321-1612-07			RES., FXD, FILM: 4.455K OHM, 0.1%, 0.125W	91637	MFF1816C44550B
R393	321-1611-07			RES., FXD, FILM: 550 OHM, 0.1%, 0.125W	91637	MFF1816C550R0B
R394	321-1612-07			RES., FXD, FILM: 4.455K OHM, 0.1%, 0.125W	91637	MFF1816C44550B
R395	321-1611-07			RES., FXD, FILM: 550 OHM, 0.1%, 0.125W	91637	MFF1816C550R0B
R396	321-1612-07			RES., FXD, FILM: 4.455K OHM, 0.1%, 0.125W	91637	MFF1816C44550B
R397	321-0813-07			RES., FXD, FILM: 495 OHM, 0.1%, 0.125W	91637	MFF1816C495R0B
R401	321-0164-00			RES., FXD, FILM: 499 OHM, 1%, 0.125W	91637	MFF1816G499R0F
R402	321-0164-00			RES., FXD, FILM: 499 OHM, 1%, 0.125W	91637	MFF1816G499R0F
R405	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R405	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R408	321-0164-00			RES., FXD, FILM: 499 OHM, 1%, 0.125W	91637	MFF1816G499ROF
R409	321-0164-00			RES., FXD, FILM: 499 OHM, 1%, 0.125W	91637	MFF1816G499ROF
R412	325-0053-00			RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R413	325-0053-00			RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R414	325-0053-00			RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R416	325-0053-00			RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R417	325-0053-00			RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R418	325-0053-00			RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R419	321-0143-00			RES., FXD, FILM: 301 OHM, 1%, 0.125W	91637	MFF1816G301ROF
R420	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200ROF
R425	321-0143-00			RES., FXD, FILM: 301 OHM, 1%, 0.125W	91637	MFF1816G301ROF
R426	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200ROF
R432	321-0202-00			RES., FXD, FILM: 1.24K OHM, 1%, 0.125W	91637	MFF1816G12400F
R433	322-0111-00			RES., FXD, FILM: 140 OHM, 1%, 0.25W	91637	MFF1421G140ROF
R434	322-0170-00			RES., FXD, FILM: 576 OHM, 1%, 0.25W	75042	CEBTO-5760F
R435	321-0202-00			RES., FXD, FILM: 1.24K OHM, 1%, 0.125W	91637	MFF1816G12400F
R436	321-0147-00			RES., FXD, FILM: 332 OHM, 1%, 0.125W	91637	MFF1816G332ROF
R437	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R438	321-0155-00			RES., FXD, FILM: 402 OHM, 1%, 0.125W	91637	MFF1816G402ROF
R439	322-0114-00			RES., FXD, FILM: 150 OHM, 1%, 0.25W	75042	CEBTO-1500F
R440	317-0200-00			RES., FXD, CMPSN: 20 OHM, 5%, 0.125W	01121	BB2005
R441	321-0085-00			RES., FXD, FILM: 75 OHM, 1%, 0.125W	91637	MFF1816G75R00F
R442	321-0202-00			RES., FXD, FILM: 1.24K OHM, 1%, 0.125W	91637	MFF1816G12400F
R443	322-0111-00			RES., FXD, FILM: 140 OHM, 1%, 0.25W	91637	MFF1421G140ROF
R444	322-0170-00			RES., FXD, FILM: 576 OHM, 1%, 0.25W	75042	CEBTO-5760F
R445	321-0202-00			RES., FXD, FILM: 1.24K OHM, 1%, 0.125W	91637	MFF1816G12400F
R446	321-0147-00			RES., FXD, FILM: 332 OHM, 1%, 0.125W	91637	MFF1816G332ROF
R447	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R448	321-0155-00			RES., FXD, FILM: 402 OHM, 1%, 0.125W	91637	MFF1816G402ROF
R451	321-0218-00			RES., FXD, FILM: 1.82K OHM, 1%, 0.125W	91637	MFF1816G18200F
R452	321-0242-00			RES., FXD, FILM: 3.24K OHM, 1%, 0.125W	91637	MFF1816G32400F
R454	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R455	311-1236-00			RES., VAR, NONWIR: 250 OHM, 10%, 0.50W	73138	72X-22-0-251K
R456	321-0062-00			RES., FXD, FILM: 43.2 OHM, 1%, 0.125W	91637	MFF1816G43R20F
R462	322-0151-00			RES., FXD, FILM: 365 OHM, 1%, 0.25W	75042	CEBTO-3650F
R464	321-0201-00			RES., FXD, FILM: 1.21K OHM, 1%, 0.125W	91637	MFF1816G12100F
R465	321-0285-00			RES., FXD, FILM: 9.09K OHM, 1%, 0.125W	91637	MFF1816G90900F
R473	322-0239-00			RES., FXD, FILM: 3.01K OHM, 1%, 0.25W	75042	CEBTO-3011F
R474	311-1248-00			RES., VAR, NONWIR: 500 OHM, 10%, 0.50W	73138	72X-23-0-501K
R476	317-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R477	317-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R478	322-0085-00			RES., FXD, FILM: 75 OHM, 1%, 0.25W	75042	CEBTO-75R00F
R479	311-1936-00			RES., FVAR, NONWIR: 50 OHM, 20%, 0.5W	73138	MODEL 72X
R480	311-1237-00			RES., VAR, NONWIR: 1K OHM, 10%, 0.50W	32997	3386X-T07-102
R481	321-0179-00			RES., FXD, FILM: 715 OHM, 1%, 0.125W	91637	MFF1816G715ROF
R482	321-0182-00			RES., FXD, FILM: 768 OHM, 1%, 0.125W	91637	MFF1816G768ROF
R483	317-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.125W	01121	BB1005
R484	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R485	311-1936-00			RES., VAR, NONWIR: 50 OHM, 20%, 0.5W	73138	72-232-0
R486	321-0143-00			RES., FXD, FILM: 301 OHM, 1%, 0.125W	91637	MFF1816G301ROF
R490	311-1237-00			RES., VAR, NONWIR: 1K OHM, 10%, 0.50W	32997	3386X-T07-102
R491	321-0179-00			RES., FXD, FILM: 715 OHM, 1%, 0.125W	91637	MFF1816G715ROF

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff Dscont	Name & Description	Mfr Code	Mfr Part Number
R492	321-0182-00		RES., FXD, FILM: 768 OHM, 1%, 0.125W	91637	MFF1816G768ROF
R493	317-0100-00		RES., FXD, CMPSN: 10 OHM, 5%, 0.125W	01121	BB1005
R494	315-0510-00		RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R495	322-0145-00		RES., FXD, FILM: 316 OHM, 1%, 0.25W	75042	CEBTO-3160F
R496	321-0143-00		RES., FXD, FILM: 301 OHM, 1%, 0.125W	91637	MFF1816G301ROF
R497	322-0175-00		RES., FXD, FILM: 649 OHM, 1%, 0.25W	75042	CEBTO-6490F
R498	321-0143-00		RES., FXD, FILM: 301 OHM, 1%, 0.125W	91637	MFF1816G301ROF
R499	315-0510-00		RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R501	321-0289-00		RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R502	321-0289-00		RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R504	321-0355-00		RES., FXD, FILM: 48.7K OHM, 1%, 0.125W	91637	MFF1816G48701F
R505	321-0335-00		RES., FXD, FILM: 30.1K OHM, 1%, 0.125W	91637	MFF1816G30101F
R511	315-0204-00		RES., FXD, CMPSN: 200K OHM, 5%, 0.25W	01121	CB2045
R512	311-1214-00		RES., VAR, NONWIR: 200K OHM, 20%, 0.50W	01121	E2B204
R513	315-0203-00		RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R514	315-0104-00		RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R515	311-1235-00		RES., VAR, NONWIR: 100K OHM, 20%, 0.50W	32997	3386F-T04-104
R516	315-0163-00		RES., FXD, CMPSN: 16K OHM, 5%, 0.25W	01121	CB1635
R519	315-0104-00		RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R520	311-1232-00		RES., VAR, NONWIR: 50K OHM, 20%, 0.50W	32997	3386F-T04-503
R521	315-0822-00		RES., FXD, CMPSN: 8.2K OHM, 5%, 0.25W	01121	CB8225
R524	315-0513-00		RES., FXD, CMPSN: 51K OHM, 5%, 0.25W	01121	CB5135
R525	311-1230-00		RES., VAR, NONWIR: 20K OHM, 20%, 0.50W	32997	3386F-T04-203
R526	315-0183-00		RES., FXD, CMPSN: 18K OHM, 5%, 0.25W	01121	CB1835
R529	315-0243-00		RES., FXD, CMPSN: 24K OHM, 5%, 0.25W	01121	CB2435
R530	311-1230-00		RES., VAR, NONWIR: 20K OHM, 20%, 0.50W	32997	3386F-T04-203
R531	315-0474-00		RES., FXD, CMPSN: 470K OHM, 5%, 0.25W	01121	CB4745
R532	315-0474-00		RES., FXD, CMPSN: 470K OHM, 5%, 0.25W	01121	CB4745
R535	311-1235-00		RES., VAR, NONWIR: 100K OHM, 20%, 0.50W	32997	3386F-T04-104
R536	315-0104-00		RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R537	315-0564-00		RES., FXD, CMPSN: 560K OHM, 5%, 0.25W	01121	CB5645
R538	315-0243-00		RES., FXD, CMPSN: 24K OHM, 5%, 0.25W	01121	CB2435
R542	323-0168-00		RES., FXD, FILM: 549 OHM, 1%, 0.50W	75042	CECTO-5490F
R543	321-0065-00		RES., FXD, FILM: 46.4 OHM, 1%, 0.125W	91637	MFF1816G46R40F
R547	321-0084-00		RES., FXD, FILM: 73.2 OHM, 1%, 0.125W	91637	MFF1816G73R20F
R548	323-0168-00		RES., FXD, FILM: 549 OHM, 1%, 0.50W	75042	CECTO-5490F
R549	321-0010-00		RES., FXD, FILM: 12.4 OHM, 1%, 0.125W	91637	MFF1816G12R40F
R550	323-0136-00		RES., FXD, FILM: 255 OHM, 1%, 0.50W	91637	MFF1226G255ROF
R552	315-0512-00		RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R555	315-0102-00		RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R556	321-0126-00		RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200ROF
R557	321-0237-00		RES., FXD, FILM: 2.87K OHM, 1%, 0.125W	91637	MFF1816G28700F
R558	321-0126-00		RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200ROF
R559A, B	317-0103-00		RES., FXD, CMPSN: 10K OHM, 5%, 0.125W	01121	BB1035
R601	321-0289-00		RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R602	321-0289-00		RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R604	321-0335-00		RES., FXD, FILM: 30.1K OHM, 1%, 0.125W	91637	MFF1816G30101F
R605	321-0335-00		RES., FXD, FILM: 30.1K OHM, 1%, 0.125W	91637	MFF1816G30101F
R611	315-0204-00		RES., FXD, CMPSN: 200K OHM, 5%, 0.25W	01121	CB2045
R612	311-1214-00		RES., VAR, NONWIR: 200K OHM, 20%, 0.50W	01121	E2B204
R613	315-0203-00		RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R614	315-0104-00		RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R615	311-1235-00		RES., VAR, NONWIR: 100K OHM, 20%, 0.50W	32997	3386F-T04-104

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R616	315-0163-00			RES., FXD, CMPSN: 16K OHM, 5%, 0.25W	01121	CB1635
R619	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R620	311-1232-00			RES., VAR, NONWIR: 50K OHM, 20%, 0.50W	32997	3386F-T04-503
R621	315-0822-00			RES., FXD, CMPSN: 8.2K OHM, 5%, 0.25W	01121	CB8225
R624	315-0513-00			RES., FXD, CMPSN: 51K OHM, 5%, 0.25W	01121	CB5135
R625	311-1230-00			RES., VAR, NONWIR: 20K OHM, 20%, 0.50W	32997	3386F-T04-203
R626	315-0183-00			RES., FXD, CMPSN: 18K OHM, 5%, 0.25W	01121	CB1835
R629	315-0243-00			RES., FXD, CMPSN: 24K OHM, 5%, 0.25W	01121	CB2435
R630	311-1230-00			RES., VAR, NONWIR: 20K OHM, 20%, 0.50W	32997	3386F-T04-203
R631	315-0474-00			RES., FXD, CMPSN: 470K OHM, 5%, 0.25W	01121	CB4745
R632	315-0474-00			RES., FXD, CMPSN: 470K OHM, 5%, 0.25W	01121	CB4745
R638	315-0243-00			RES., FXD, CMPSN: 24K OHM, 5%, 0.25W	01121	CB2435
R642	323-0168-00			RES., FXD, FILM: 549 OHM, 1%, 0.50W	75042	CECT0-5490F
R643	321-0065-00			RES., FXD, FILM: 46.4 OHM, 1%, 0.125W	91637	MFF1816G46R40F
R647	321-0084-00			RES., FXD, FILM: 73.2 OHM, 1%, 0.125W	91637	MFF1816G73R20F
R648	323-0168-00			RES., FXD, FILM: 549 OHM, 1%, 0.50W	75042	CECT0-5490F
R649	321-0010-00			RES., FXD, FILM: 12.4 OHM, 1%, 0.125W	91637	MFF1816G12R40F
R650	323-0136-00			RES., FXD, FILM: 255 OHM, 1%, 0.50W	91637	MFF1226G255ROF
R651	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R652	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R653	315-0472-00			RES., FXD, CMPSN: 4.7K OHM, 5%, 0.25W	01121	CB4725
R654	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R655	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R656	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200ROF
R657	321-0237-00			RES., FXD, FILM: 2.87K OHM, 1%, 0.125W	91637	MFF1816G28700F
R658	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200ROF
R659	321-0080-00			RES., FXD, FILM: 66.5 OHM, 1%, 0.125W	91637	MFF1816G66R50F
R659A, B	317-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.125W	01121	BB1035
R671	321-0246-00			RES., FXD, FILM: 3.57K OHM, 1%, 0.125W	91637	MFF1816G35700F
R672	321-0295-00			RES., FXD, FILM: 11.5K OHM, 1%, 0.125W	91637	MFF1816G11501F
R675	315-0272-00			RES., FXD, CMPSN: 2.7K OHM, 5%, 0.25W	01121	CB2725
R680	321-0284-00			RES., FXD, FILM: 8.87K OHM, 1%, 0.125W	91637	MFF1816G88700F
R681	321-0296-00			RES., FXD, FILM: 11.8K OHM, 1%, 0.125W	91637	MFF1816G11801F
R682	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R683	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R684	307-0063-00			RES., FXD, CMPSN: 9.1 OHM, 5%, 0.50W	01121	EB91G5
R690	321-0279-00			RES., FXD, FILM: 7.87K OHM, 1%, 0.125W	91637	MFF1816G78700F
R691	321-0322-00			RES., FXD, FILM: 22.1K OHM, 1%, 0.125W	91637	MFF1816G22101F
R694	315-0562-00			RES., FXD, CMPSN: 5.6K OHM, 5%, 0.25W	01121	CB5625
R700	321-0318-00			RES., FXD, FILM: 20K OHM, 1%, 0.125W	91637	MFF1816G20001F
R701	311-1232-00			RES., VAR, NONWIR: 50K OHM, 20%, 0.50W	32997	3386F-T04-503
R702	315-0224-00			RES., FXD, CMPSN: 220K OHM, 5%, 0.25W	01121	CB2245
R703	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R704	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R705	307-0092-00			RES., FXD, CMPSN: 15 OHM, 5%, 0.1W	23223	15-E-5T
R711	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R712	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R714	315-0114-00			RES., FXD, CMPSN: 110K OHM, 5%, 0.25W	01121	CB1145
R718	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R722	315-0432-00			RES., FXD, CMPSN: 4.3K OHM, 5%, 0.25W	01121	CB4325
R730	315-0302-00			RES., FXD, CMPSN: 3K OHM, 5%, 0.25W	01121	CB3025
R731	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R732	315-0511-00			RES., FXD, CMPSN: 510 OHM, 5%, 0.25W	01121	CB5115

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff Dscont	Name & Description	Mfr Code	Mfr Part Number
R733	315-0203-00		RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R740	311-1232-00		RES., VAR, NONWIR: 50K OHM, 20%, 0.50W	32997	3386F-T04-503
R742	321-0094-00		RES., FXD, FILM: 93.1 OHM, 1%, 0.125W	91637	MFF1816G93R10F
R743	321-0185-00		RES., FXD, FILM: 825 OHM, 1%, 0.125W	91637	MFF1816G825R0F
R744	321-0223-00		RES., FXD, FILM: 2.05K OHM, 1%, 0.125W	91637	MFF1816G20500F
R747	322-0178-00		RES., FXD, FILM: 698 OHM, 1%, 0.25W	75042	CEBT0-6980F
R748	321-0233-00		RES., FXD, FILM: 2.61K OHM, 1%, 0.125W	91637	MFF1816G26100F
R749	321-0095-00		RES., FXD, FILM: 95.3 OHM, 1%, 0.125W	91637	MFF1816G95R30F
R750	321-0332-00		RES., FXD, FILM: 28K OHM, 1%, 0.125W	91637	MFF1816G28001F
R751	321-0165-00		RES., FXD, FILM: 511 OHM, 1%, 0.125W	91637	MFF1816G511R0F
R752	321-0228-00		RES., FXD, FILM: 2.32K OHM, 1%, 0.125W	91637	MFF1816G23200F
R753	321-0190-00		RES., FXD, FILM: 931 OHM, 1%, 0.125W	91637	MFF1816G931R0F
R754	321-0223-00		RES., FXD, FILM: 2.05K OHM, 1%, 0.125W	91637	MFF1816G20500F
R757	322-0178-00		RES., FXD, FILM: 698 OHM, 1%, 0.25W	75042	CEBT0-6980F
R758	321-0233-00		RES., FXD, FILM: 2.61K OHM, 1%, 0.125W	91637	MFF1816G26100F
R759	321-0095-00		RES., FXD, FILM: 95.3 OHM, 1%, 0.125W	91637	MFF1816G95R30F
R761	321-0278-00		RES., FXD, FILM: 7.68K OHM, 1%, 0.125W	91637	MFF1816G76800F
R762	321-0124-00		RES., FXD, FILM: 191 OHM, 1%, 0.125W	91637	MFF1816G191R0F
R763	321-0109-00		RES., FXD, FILM: 133 OHM, 1%, 0.125W	91637	MFF1816G133R0F
R764	321-0117-00		RES., FXD, FILM: 162 OHM, 1%, 0.125W	91637	MFF1816G162R0F
R765	321-0228-00		RES., FXD, FILM: 2.32K OHM, 1%, 0.125W	91637	MFF1816G23200F
R767	321-0175-00		RES., FXD, FILM: 649 OHM, 1%, 0.125W	91637	MFF1816G649R0F
R772	321-0124-00		RES., FXD, FILM: 191 OHM, 1%, 0.125W	91637	MFF1816G191R0F
R773	321-0109-00		RES., FXD, FILM: 133 OHM, 1%, 0.125W	91637	MFF1816G133R0F
R774	321-0117-00		RES., FXD, FILM: 162 OHM, 1%, 0.125W	91637	MFF1816G162R0F
R775	321-0182-00		RES., FXD, FILM: 768 OHM, 1%, 0.125W	91637	MFF1816G768R0F
R777	321-0127-00		RES., FXD, FILM: 205 OHM, 1%, 0.125W	91637	MFF1816G205R0F
R780	315-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R781	321-0193-00		RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R782	321-0239-00		RES., FXD, FILM: 3.01K OHM, 1%, 0.125W	91637	MFF1816G30100F
R785	311-1230-00		RES., VAR, NONWIR: 20K OHM, 20%, 0.50W	32997	3386F-T04-203
R786	315-0513-00		RES., FXD, CMPSN: 51K OHM, 5%, 0.25W	01121	CB5135
R787	311-1214-00		RES., VAR, NONWIR: 200K OHM, 20%, 0.50W	01121	E2B204
R788	315-0623-00		RES., FXD, CMPSN: 62K OHM, 5%, 0.25W	01121	CB6235
R789	315-0334-00		RES., FXD, CMPSN: 330K OHM, 5%, 0.25W	01121	CB3345
R791	311-1214-00		RES., VAR, NONWIR: 200K OHM, 20%, 0.50W	01121	E2B204
R792	315-0473-00		RES., FXD, CMPSN: 47K OHM, 5%, 0.25W	01121	CB4735
R793	315-0513-00		RES., FXD, CMPSN: 51K OHM, 5%, 0.25W	01121	CB5135
R795	311-1214-00		RES., VAR, NONWIR: 200K OHM, 20%, 0.50W	01121	E2B204
R796	315-0363-00		RES., FXD, CMPSN: 36K OHM, 5%, 0.25W	01121	CB3635
R797	315-0513-00		RES., FXD, CMPSN: 51K OHM, 5%, 0.25W	01121	CB5135
R801	311-1214-00		RES., VAR, NONWIR: 200K OHM, 20%, 0.50W	01121	E2B204
R802	315-0333-00		RES., FXD, CMPSN: 33K OHM, 5%, 0.25W	01121	CB3335
R803	315-0513-00		RES., FXD, CMPSN: 51K OHM, 5%, 0.25W	01121	CB5135
R804	315-0154-00		RES., FXD, CMPSN: 150K OHM, 5%, 0.25W	01121	CB1545
R805	315-0563-00		RES., FXD, CMPSN: 56K OHM, 5%, 0.25W	01121	CB5635
R806	311-1214-00		RES., VAR, NONWIR: 200K OHM, 20%, 0.50W	01121	E2B204
R808	315-0433-00		RES., FXD, CMPSN: 43K OHM, 5%, 0.25W	01121	CB4335
R814	321-0143-00		RES., FXD, FILM: 301 OHM, 1%, 0.125W	91637	MFF1816G301R0F
R815	321-0090-00		RES., FXD, FILM: 84.5 OHM, 1%, 0.125W	91637	MFF1816G84R50F
R821	321-0104-00		RES., FXD, FILM: 118 OHM, 1%, 0.125W	91637	MFF1816G118R0F
R823	315-0151-00		RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R824	321-0143-00		RES., FXD, FILM: 301 OHM, 1%, 0.125W	91637	MFF1816G301R0F

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R825	321-0057-00			RES., FXD, FILM: 38.3 OHM, 1%, 0.125W	91637	MFF1816G38R30F
R830	311-1266-00			RES., VAR, NONWIR: 2.5K OHM, 10%, 0.5W	32997	3329P-L58-252
R831	321-0105-00			RES., FXD, FILM: 121 OHM, 1%, 0.125W	91637	MFF1816G121ROF
R832	321-0105-00			RES., FXD, FILM: 121 OHM, 1%, 0.125W	91637	MFF1816G121ROF
R836	311-1260-00			RES., VAR, NONWIR: 250 OHM, 10%, 0.50W	32997	3329P-L58-251
R837	321-0068-00			RES., FXD, FILM: 49.9 OHM, 1%, 0.125W	91637	MFF1816G49R90F
R838	321-0068-00			RES., FXD, FILM: 49.9 OHM, 1%, 0.125W	91637	MFF1816G49R90F
R849	322-0104-00			RES., FXD, FILM: 118 OHM, 1%, 0.25W	91637	MFF1421G118ROF
R854	321-0170-00			RES., FXD, FILM: 576 OHM, 1%, 0.125W	91637	MFF1816G576ROF
R855	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200ROF
R856	321-0238-00			RES., FXD, FILM: 2.94K OHM, 1%, 0.125W	91637	MFF1816G29400F
R857	317-0122-00			RES., FXD, CMPSN: 1.2K OHM, 5%, 0.125W	01121	BB1225
R860	315-0822-00			RES., FXD, CMPSN: 8.2K OHM, 5%, 0.25W	01121	CB8225
R861	315-0272-00			RES., FXD, CMPSN: 2.7K OHM, 5%, 0.25W	01121	CB2725
R862	301-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.50W	01121	EB1015
R863	315-0362-00			RES., FXD, CMPSN: 3.6K OHM, 5%, 0.25W	01121	CB3625
R864	315-0133-00			RES., FXD, CMPSN: 13K OHM, 5%, 0.25W	01121	CB1335
R865	315-0303-00			RES., FXD, CMPSN: 30K OHM, 5%, 0.25W	01121	CB3035
R866	315-0682-00			RES., FXD, CMPSN: 6.8K OHM, 5%, 0.25W	01121	CB6825
R870	315-0431-00			RES., FXD, CMPSN: 430 OHM, 5%, 0.25W	01121	CB4315
R871	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R872	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R873	321-0426-00			RES., FXD, FILM: 267K OHM, 1%, 0.125W	91637	MFF1816G26702F
R874	321-0377-00			RES., FXD, FILM: 82.5K OHM, 1%, 0.125W	24546	NA55D8252F
R875	315-0623-00			RES., FXD, CMPSN: 62K OHM, 5%, 0.25W	01121	CB6235
R876	315-0243-00			RES., FXD, CMPSN: 24K OHM, 5%, 0.25W	01121	CB2435
R877	301-0242-00			RES., FXD, CMPSN: 2.4K OHM, 5%, 0.50W	01121	EB2425
R878	308-0243-00			RES., FXD, WW: 240 OHM, 5%, 3W	91637	CW2BB240R0J
R881	321-0265-00			RES., FXD, FILM: 5.62K OHM, 1%, 0.125W	91637	MFF1816G56200F
R882	321-0201-00			RES., FXD, FILM: 1.21K OHM, 1%, 0.125W	91637	MFF1816G12100F
R883	315-0392-00			RES., FXD, CMPSN: 3.9K OHM, 5%, 0.25W	01121	CB3925
R884	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R886	321-0328-00			RES., FXD, FILM: 25.5K OHM, 1%, 0.125W	91637	MFF1816G25501F
R887	315-0682-00			RES., FXD, CMPSN: 6.8K OHM, 5%, 0.25W	01121	CB6825
R888	321-0289-00			RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R891	315-0752-00			RES., FXD, CMPSN: 7.5K OHM, 5%, 0.25W	01121	CB7525
R892	301-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.50W	01121	EB1025
R893	308-0298-00			RES., FXD, WW: 560 OHM, 5%, 3W	91637	CW2B-B560R0J
R894	321-0001-00			RES., FXD, FILM: 10 OHM, 1%, 0.125W	75042	CEAT0-10R00F
R902	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R905	321-0186-00			RES., FXD, FILM: 845 OHM, 1%, 0.125W	91637	MFF1816G845ROF
R906	321-0252-00			RES., FXD, FILM: 4.12K OHM, 1%, 0.125W	91637	MFF1816G41200F
R913	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100ROF
R921	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R922	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R923	323-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.50W	75042	CECT0-1001F
R924	321-0069-00			RES., FXD, FILM: 51.1 OHM, 1%, 0.125W	91637	MFF1816G51R10F
R926	315-0272-00			RES., FXD, CMPSN: 2.7K OHM, 5%, 0.25W	01121	CB2725
R927	315-0203-00			RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R928	323-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.50W	75042	CECT0-1001F
R932	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100ROF
R933	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100ROF
R934	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100ROF

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff Dscont	Name & Description	Mfr Code	Mfr Part Number
R941	317-0103-00		RES., FXD, CMPSN: 10K OHM, 5%, 0.125W	01121	BB1035
R942	317-0303-00		RES., FXD, CMPSN: 30K OHM, 5%, 0.125W	01121	BB3035
R943	321-0289-00		RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R944	321-0335-00		RES., FXD, FILM: 30.1K OHM, 1%, 0.125W	91637	MFF1816G30101F
R945	311-1222-00		RES., VAR, NONWIR: 100 OHM, 20%, 0.50W	32997	3386F-T04-101
R946	315-0680-00		RES., FXD, CMPSN: 68 OHM, 5%, 0.25W	01121	CB6805
R948	321-0097-00		RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100ROF
R949	321-0251-00		RES., FXD, FILM: 4.02K OHM, 1%, 0.125W	91637	MFF1816G40200F
R950	311-1225-00		RES., VAR, NONWIR: 1K OHM, 20%, 0.50W	32997	3386F-T04-102
R952	311-1227-00		RES., VAR, NONWIR: 5K OHM, 20%, 0.50W	32997	3386F-T04-502
R955	311-1230-00		RES., VAR, NONWIR: 20K OHM, 20%, 0.50W	32997	3386F-T04-203
R958	311-1232-00		RES., VAR, NONWIR: 50K OHM, 20%, 0.50W	32997	3386F-T04-503
R959	321-0294-00		RES., FXD, FILM: 11.3K OHM, 1%, 0.125W	91637	MFF1816G11301F
R962	321-0102-00		RES., FXD, FILM: 113 OHM, 1%, 0.125W	91637	MFF1816G113ROF
R963	323-0127-00		RES., FXD, FILM: 205 OHM, 1%, 0.50W	75042	CECT0-2050F
R964	321-0267-00		RES., FXD, FILM: 5.9K OHM, 1%, 0.125W	91637	MFF1816G59000F
R965	311-1224-00		RES., VAR, NONWIR: 500 OHM, 20%, 0.50W	32997	3386F-T04-501
R966	321-0252-00		RES., FXD, FILM: 4.12K OHM, 1%, 0.125W	91637	MFF1816G41200F
R967	321-0102-00		RES., FXD, FILM: 113 OHM, 1%, 0.125W	91637	MFF1816G113ROF
R968	323-0114-00		RES., FXD, FILM: 150 OHM, 1%, 0.50W	75042	CECT0-1500F
R969	323-0114-00		RES., FXD, FILM: 150 OHM, 1%, 0.50W	75042	CECT0-1500F
R971	317-0103-00		RES., FXD, CMPSN: 10K OHM, 5%, 0.125W	01121	BB1035
R972	317-0303-00		RES., FXD, CMPSN: 30K OHM, 5%, 0.125W	01121	BB3035
R973	321-0289-00		RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R974	321-0335-00		RES., FXD, FILM: 30.1K OHM, 1%, 0.125W	91637	MFF1816G30101F
R975	311-1222-00		RES., VAR, NONWIR: 100 OHM, 20%, 0.50W	32997	3386F-T04-101
R976	315-0680-00		RES., FXD, CMPSN: 68 OHM, 5%, 0.25W	01121	CB6805
R978	321-0097-00		RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100ROF
R979	321-0251-00		RES., FXD, FILM: 4.02K OHM, 1%, 0.125W	91637	MFF1816G40200F
R980	311-1225-00		RES., VAR, NONWIR: 1K OHM, 20%, 0.50W	32997	3386F-T04-102
R982	311-1227-00		RES., VAR, NONWIR: 5K OHM, 20%, 0.50W	32997	3386F-T04-502
R985	311-1230-00		RES., VAR, NONWIR: 20K OHM, 20%, 0.50W	32997	3386F-T04-203
R988	311-1232-00		RES., VAR, NONWIR: 50K OHM, 20%, 0.50W	32997	3386F-T04-503
R989	321-0294-00		RES., FXD, FILM: 11.3K OHM, 1%, 0.125W	91637	MFF1816G11301F
R992	321-0102-00		RES., FXD, FILM: 113 OHM, 1%, 0.125W	91637	MFF1816G113ROF
R993	323-0127-00		RES., FXD, FILM: 205 OHM, 1%, 0.50W	75042	CECT0-2050F
R994	321-0267-00		RES., FXD, FILM: 5.9K OHM, 1%, 0.125W	91637	MFF1816G59000F
R995	311-1224-00		RES., VAR, NONWIR: 500 OHM, 20%, 0.50W	32997	3386F-T04-501
R996	321-0252-00		RES., FXD, FILM: 4.12K OHM, 1%, 0.125W	91637	MFF1816G41200F
R997	321-0102-00		RES., FXD, FILM: 113 OHM, 1%, 0.125W	91637	MFF1816G113ROF
R998	323-0114-00		RES., FXD, FILM: 150 OHM, 1%, 0.50W	75042	CECT0-1500F
R999	323-0114-00		RES., FXD, FILM: 150 OHM, 1%, 0.50W	75042	CECT0-1500F
R1001	315-0563-00		RES., FXD, CMPSN: 56K OHM, 5%, 0.25W	01121	CB5635
R1002	321-0262-00		RES., FXD, FILM: 5.23K OHM, 1%, 0.125W	91637	MFF1816G52300F
R1003	315-0102-00		RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1004	321-0231-00		RES., FXD, FILM: 2.49K OHM, 1%, 0.125W	91637	MFF1816G24900F
R1005	311-1224-00		RES., VAR, NONWIR: 500 OHM, 20%, 0.50W	32997	3386F-T04-501
R1007	321-0165-00		RES., FXD, FILM: 511 OHM, 1%, 0.125W	91637	MFF1816G511ROF
R1010	315-0103-00		RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1011	321-0276-00		RES., FXD, FILM: 7.32K OHM, 1%, 0.125W	91637	MFF1816G73200F
R1012	321-0289-00		RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R1013	315-0473-00		RES., FXD, CMPSN: 47K OHM, 5%, 0.25W	01121	CB4735
R1014	315-0752-00		RES., FXD, CMPSN: 7.5K OHM, 5%, 0.25W	01121	CB7525

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1015	315-0473-00			RES., FXD, CMPSN: 47K OHM, 5%, 0.25W	01121	CB4735
R1016	321-0379-00			RES., FXD, FILM: 86.6K OHM, 1%, 0.125W	91637	MFF1816G86601F
R1017	321-0396-00			RES., FXD, FILM: 130K OHM, 1%, 0.125W	91637	MFF1816G13002F
R1018	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R1019	317-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R1020	321-0350-00			RES., FXD, FILM: 43.2K OHM, 1%, 0.125W	91637	MFF1816G43201F
R1021	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1022	315-0203-00			RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R1023	315-0511-00			RES., FXD, CMPSN: 510 OHM, 5%, 0.25W	01121	CB5115
R1024	315-0123-00			RES., FXD, CMPSN: 12K OHM, 5%, 0.25W	01121	CB1235
R1025	311-1231-00			RES., VAR, NONWIR: 25K OHM, 20%, 0.50W	32997	3386F-T04-253
R1026	315-0271-00			RES., FXD, CMPSN: 270 OHM, 5%, 0.25W	01121	CB2715
R1028	321-0291-00			RES., FXD, FILM: 10.5K OHM, 1%, 0.125W	91637	MFF1816G10501F
R1029	315-0362-00			RES., FXD, CMPSN: 3.6K OHM, 5%, 0.25W	01121	CB3625
R1030	311-1225-00			RES., VAR, NONWIR: 1K OHM, 20%, 0.50W	32997	3386F-T04-102
R1031	321-0291-00			RES., FXD, FILM: 10.5K OHM, 1%, 0.125W	91637	MFF1816G10501F
R1032	315-0221-00			RES., FXD, CMPSN: 220 OHM, 5%, 0.25W	01121	CB2215
R1033	315-0242-00			RES., FXD, CMPSN: 2.4K OHM, 5%, 0.25W	01121	CB2425
R1034	321-0192-00			RES., FXD, FILM: 976 OHM, 1%, 0.125W	91637	MFF1816G976ROF
R1035	311-1222-00			RES., VAR, NONWIR: 100 OHM, 20%, 0.50W	32997	3386F-T04-101
R1036	321-0235-00			RES., FXD, FILM: 2.74K OHM, 1%, 0.125W	91637	MFF1816G27400F
R1037	321-0192-00			RES., FXD, FILM: 976 OHM, 1%, 0.125W	91637	MFF1816G976ROF
R1040	317-0120-00			RES., FXD, CMPSN: 12 OHM, 5%, 0.125W	01121	BB1205
R1041	317-0120-00			RES., FXD, CMPSN: 12 OHM, 5%, 0.125W	01121	BB1205
R1042	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R1043	323-0064-00			RES., FXD, FILM: 45.3 OHM, 1%, 0.50W	91637	MFF1226G45R30F
R1044	315-0911-00			RES., FXD, CMPSN: 910 OHM, 5%, 0.25W	01121	CB9115
R1045	321-0380-00			RES., FXD, FILM: 88.7K OHM, 1%, 0.125W	91637	MFF1816G88701F
R1046	321-0324-00			RES., FXD, FILM: 23.2K OHM, 1%, 0.125W	91637	MFF1816G23201F
R1047	323-0606-00			RES., FXD, FILM: 60 OHM, 1%, 0.5W	19701	MF62C
R1049	321-0160-00			RES., FXD, FILM: 453 OHM, 1%, 0.125W	91637	MFF1816G453ROF
R1052	315-0821-00			RES., FXD, CMPSN: 820 OHM, 5%, 0.25W	01121	CB8215
R1054	317-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.125W	01121	BB1005
R1058	315-0131-00			RES., FXD, CMPSN: 130 OHM, 5%, 0.25W	01121	CB1315
R1059	307-0113-00			RES., FXD, CMPSN: 5.1 OHM, 5%, 0.25W	01121	CB51G5
R1060	317-0120-00			RES., FXD, CMPSN: 12 OHM, 5%, 0.125W	01121	BB1205
R1061	317-0120-00			RES., FXD, CMPSN: 12 OHM, 5%, 0.125W	01121	BB1205
R1062	311-1224-00			RES., VAR, NONWIR: 500 OHM, 20%, 0.50W	32997	3386F-T04-501
R1063	323-0064-00			RES., FXD, FILM: 45.3 OHM, 1%, 0.50W	91637	MFF1226G45R30F
R1064	315-0911-00			RES., FXD, CMPSN: 910 OHM, 5%, 0.25W	01121	CB9115
R1065	321-0380-00			RES., FXD, FILM: 88.7K OHM, 1%, 0.125W	91637	MFF1816G88701F
R1066	321-0324-00			RES., FXD, FILM: 23.2K OHM, 1%, 0.125W	91637	MFF1816G23201F
R1067	323-0606-00			RES., FXD, FILM: 60 OHM, 1%, 0.5W	19701	MF62C
R1069	315-0272-00			RES., FXD, CMPSN: 2.7K OHM, 5%, 0.25W	01121	CB2725
R1071	317-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R1072	315-0821-00			RES., FXD, CMPSN: 820 OHM, 5%, 0.25W	01121	CB8215
R1073	311-1221-00			RES., VAR, NONWIR: 50 OHM, 20%, 0.50W	32997	3386F-T04-500
R1074	317-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.125W	01121	BB1005
R1075	317-0820-00			RES., FXD, CMPSN: 82 OHM, 5%, 0.125W	01121	BB8205
R1076	323-0090-00			RES., FXD, FILM: 84.5 OHM, 1%, 0.50W	75042	CECT0-84R5F
R1077	317-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R1078	315-0131-00			RES., FXD, CMPSN: 130 OHM, 5%, 0.25W	01121	CB1315
R1079	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff Dscont	Name & Description	Mfr Code	Mfr Part Number
R1080	315-0104-00		RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1081	301-0432-00		RES., FXD, CMPSN: 4.3K OHM, 5%, 0.50W	01121	EB4325
R1082	311-1225-00		RES., VAR, NONWIR: 1K OHM, 20%, 0.50W	32997	3386F-T04-102
R1083	315-0162-00		RES., FXD, CMPSN: 1.6K OHM, 5%, 0.25W	01121	CB1625
R1084	315-0123-00		RES., FXD, CMPSN: 12K OHM, 5%, 0.25W	01121	CB1235
R1085	315-0152-00		RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1086	315-0100-00		RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R1087	315-0100-00		RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R1088	321-0261-00		RES., FXD, FILM: 5.11K OHM, 1%, 0.125W	91637	MFF1816G51100F
R1089	321-0328-00		RES., FXD, FILM: 25.5K OHM, 1%, 0.125W	91637	MFF1816G25501F
R1094	323-0069-00		RES., FXD, FILM: 51.1 OHM, 1%, 0.50W	91637	MFF1226G51R10F
R1095	323-0069-00		RES., FXD, FILM: 51.1 OHM, 1%, 0.50W	91637	MFF1226G51R10F
R1096	315-0100-00		RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R1099	307-0292-01		RES., FXD, FILM: 180 OHM	80009	307-0292-01
R1103	323-0106-00		RES., FXD, FILM: 124 OHM, 1%, 0.50W	91637	MFF1226G124ROF
R1103	-----		* OPTION 2 ONLY		
R1103	-----		* OPTION 2 ONLY		
R1104	323-0106-00		RES., FXD, FILM: 124 OHM, 1%, 0.50W	91637	MFF1226G124ROF
R1104	-----		* OPTION 2 ONLY		
R1105	311-1007-00		RES., VAR, NONWIR: 20 OHM, 20%, 0.50W	73138	82-38-0
R1105	-----		* OPTION 2 ONLY		
R1106	321-0130-00		RES., FXD, FILM: 221 OHM, 1%, 0.125W	91637	MFF1816G221ROF
R1106	-----		* OPTION 2 ONLY		
R1110	311-1265-00		RES., VAR, NONWIR: 2K OHM, 10%, 0.50W	32997	3329P-L58-202
R1110	-----		* OPTION 2 ONLY		
R1112	311-1265-00		RES., VAR, NONWIR: 2K OHM, 10%, 0.50W	32997	3329P-L58-202
R1112	-----		* OPTION 2 ONLY		
R1113	311-1265-00		RES., VAR, NONWIR: 2K OHM, 10%, 0.50W	32997	3329P-L58-202
R1113	-----		* OPTION 2 ONLY		
R1114	311-1261-00		RES., VAR, NONWIR: 500 OHM, 10%, 0.50W	32997	3329P-L58-501
R1114	-----		* OPTION 2 ONLY		
R1116	325-0053-00		RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R1116	-----		* OPTION 2 ONLY		
R1118	321-0381-00		RES., FXD, FILM: 90.9K OHM, 1%, 0.125W	91637	MFF1816G90901F
R1118	-----		* OPTION 2 ONLY		
R1119	321-0323-00		RES., FXD, FILM: 22.6K OHM, 1%, 0.125W	91637	MFF1816G22601F
R1119	-----		* OPTION 2 ONLY		
R1120	311-1227-00		RES., VAR, NONWIR: 5K OHM, 20%, 0.50W	32997	3386F-T04-502
R1120	-----		* OPTION 2 ONLY		
R1126	321-0126-00		RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200ROF
R1126	-----		* OPTION 2 ONLY		
R1127	317-0220-00		RES., FXD, CMPSN: 22 OHM, 5%, 0.125W	01121	BB2205
R1127	-----		* OPTION 2 ONLY		
R1136	325-0053-00		RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R1136	-----		* OPTION 2 ONLY		
R1140	321-0318-00		RES., FXD, FILM: 20K OHM, 1%, 0.125W	91637	MFF1816G20001F
R1140	-----		* OPTION 2 ONLY		
R1141	321-0335-00		RES., FXD, FILM: 30.1K OHM, 1%, 0.125W	91637	MFF1816G30101F
R1141	-----		* OPTION 2 ONLY		
R1142	315-0470-00		RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R1142	-----		* OPTION 2 ONLY		
R1144	321-0265-00		RES., FXD, FILM: 5.62K OHM, 1%, 0.125W	91637	MFF1816G56200F
R1144	-----		* OPTION 2 ONLY		

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1145	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R1145	-----			* OPTION 2 ONLY		
R1150	323-0133-00			RES., FXD, FILM: 237 OHM, 1%, 0.50W	75042	CECT0-2370F
R1150	-----			* OPTION 2 ONLY		
R1152	322-0616-00			RES., FXD, FILM: 21.4 OHM, 1%, 0.25W	75042	CEBT0-21R40F
R1152	-----			* OPTION 2 ONLY		
R1153	321-0075-00			RES., FXD, FILM: 59 OHM, 1%, 0.125W	91637	MFF1816G59R00F
R1153	-----			* OPTION 2 ONLY		
R1154	321-0010-00			RES., FXD, FILM: 12.4 OHM, 1%, 0.125W	91637	MFF1816G12R40F
R1154	-----			* OPTION 2 ONLY		
R1155	321-0144-00			RES., FXD, FILM: 309 OHM, 1%, 0.125W	91637	MFF1816G309R0F
R1155	-----			* OPTION 2 ONLY		
R1156	311-1259-00			RES., VAR, NONWIR: 100 OHM, 10%, 0.50W	32997	3329P-L58-101
R1156	-----			* OPTION 2 ONLY		
R1157	317-0620-00			RES., FXD, CMPSN: 62 OHM, 5%, 0.125W	01121	BB6205
R1157	-----			* OPTION 2 ONLY		
R1160	323-0133-00			RES., FXD, FILM: 237 OHM, 1%, 0.50W	75042	CECT0-2370F
R1160	-----			* OPTION 2 ONLY		
R1162	301-0681-00			RES., FXD, CMPSN: 680 OHM, 5%, 0.50W	01121	EB6815
R1162	-----			* OPTION 2 ONLY		
R1163	321-0075-00			RES., FXD, FILM: 59 OHM, 1%, 0.125W	91637	MFF1816G59R00F
R1163	-----			* OPTION 2 ONLY		
R1164	321-0010-00			RES., FXD, FILM: 12.4 OHM, 1%, 0.125W	91637	MFF1816G12R40F
R1164	-----			* OPTION 2 ONLY		
R1165	321-0144-00			RES., FXD, FILM: 309 OHM, 1%, 0.125W	91637	MFF1816G309R0F
R1165	-----			* OPTION 2 ONLY		
R1166	301-0511-00			RES., FXD, CMPSN: 510 OHM, 5%, 0.50W	01121	EB5115
R1166	-----			* OPTION 2 ONLY		
R1205	304-0270-00			RES., FXD, CMPSN: 27 OHM, 10%, 1W	01121	GB2701
R1209	304-0473-00			RES., FXD, CMPSN: 47K OHM, 10%, 1W	01121	GB4731
R1210	303-0304-00			RES., FXD, CMPSN: 300K OHM, 5%, 1W	01121	GB3045
R1213	304-0473-00			RES., FXD, CMPSN: 47K OHM, 10%, 1W	01121	GB4731
R1219	302-0565-00			RES., FXD, CMPSN: 5.6M OHM, 10%, 0.50W	01121	EB5651
R1221	304-0154-00			RES., FXD, CMPSN: 150K OHM, 10%, 1W	01121	GB1541
R1225	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1231	307-0057-00			RES., FXD, CMPSN: 5.1 OHM, 5%, 0.50W	01121	EB51G5
R1232	315-0220-00			RES., FXD, CMPSN: 22 OHM, 5%, 0.25W	01121	CB2205
R1236	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1238	315-0333-00			RES., FXD, CMPSN: 33K OHM, 5%, 0.25W	01121	CB3335
R1239	307-0057-00			RES., FXD, CMPSN: 5.1 OHM, 5%, 0.50W	01121	EB51G5
R1240	315-0220-00			RES., FXD, CMPSN: 22 OHM, 5%, 0.25W	01121	CB2205
R1241	315-0753-00			RES., FXD, CMPSN: 75K OHM, 5%, 0.25W	01121	CB7535
R1242	315-0303-00			RES., FXD, CMPSN: 30K OHM, 5%, 0.25W	01121	CB3035
R1243	315-0204-00			RES., FXD, CMPSN: 200K OHM, 5%, 0.25W	01121	CB2045
R1244	315-0270-00			RES., FXD, CMPSN: 27 OHM, 5%, 0.25W	01121	CB2705
R1245	315-0182-00			RES., FXD, CMPSN: 1.8K OHM, 5%, 0.25W	01121	CB1825
R1247	301-0184-00			RES., FXD, CMPSN: 180K OHM, 5%, 0.50W	01121	EB1845
R1252	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R1259	315-0222-00			RES., FXD, CMPSN: 2.2K OHM, 5%, 0.25W	01121	CB2225
R1260	315-0224-00			RES., FXD, CMPSN: 220K OHM, 5%, 0.25W	01121	CB2245
R1261	315-0123-00			RES., FXD, CMPSN: 12K OHM, 5%, 0.25W	01121	CB1235
R1262	315-0301-00			RES., FXD, CMPSN: 300 OHM, 5%, 0.25W	01121	CB3015
R1263	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff Dscont	Name & Description	Mfr Code	Mfr Part Number
R1264	315-0102-00		RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1266	315-0202-00		RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R1267	315-0154-00		RES., FXD, CMPSN: 150K OHM, 5%, 0.25W	01121	CB1545
R1270	315-0560-00		RES., FXD, CMPSN: 56 OHM, 5%, 0.25W	01121	CB5605
R1271	315-0560-00		RES., FXD, CMPSN: 56 OHM, 5%, 0.25W	01121	CB5605
R1274	321-0346-00		RES., FXD, FILM: 39.2K OHM, 1%, 0.125W	91637	MFF1816G39201F
R1280	315-0471-00		RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1281	321-0334-00		RES., FXD, FILM: 29.4K OHM, 1%, 0.125W	91637	MFF1816G29401F
R1282	321-0340-00		RES., FXD, FILM: 34K OHM, 1%, 0.125W	91637	MFF1816G34001F
R1283	321-0193-00		RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R1284	321-0008-00		RES., FXD, FILM: 11.8 OHM, 1%, 0.125W	91637	MFF1816G11R80F
R1286	321-0283-00		RES., FXD, FILM: 8.66K OHM, 1%, 0.125W	91637	MFF1816G86600F
R1287	321-0282-00		RES., FXD, FILM: 8.45K OHM, 1%, 0.125W	91637	MFF1816G84500F
R1288	315-0102-00		RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1290	315-0272-00		RES., FXD, CMPSN: 2.7K OHM, 5%, 0.25W	01121	CB2725
R1292	315-0105-00		RES., FXD, CMPSN: 1M OHM, 5%, 0.25W	01121	CB1055
R1293	311-1239-00		RES., VAR, NONWIR: 2.5K OHM, 0.5W	73138	72X-76-252K
R1294	315-0203-00		RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R1295	321-0419-00		RES., FXD, FILM: 226K OHM, 1%, 0.125W	91637	MFF1816G22602F
R1320	315-0150-00		RES., FXD, CMPSN: 15 OHM, 5%, 0.25W	01121	CB1505
R1321	315-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1327	301-0391-00		RES., FXD, CMPSN: 390 OHM, 5%, 0.50W	01121	EB3915
R1361	315-0473-00		RES., FXD, CMPSN: 47K OHM, 5%, 0.25W	01121	CB4735
R1362	315-0472-00		RES., FXD, CMPSN: 4.7K OHM, 5%, 0.25W	01121	CB4725
R1371	315-0472-00		RES., FXD, CMPSN: 4.7K OHM, 5%, 0.25W	01121	CB4725
R1373	315-0753-00		RES., FXD, CMPSN: 75K OHM, 5%, 0.25W	01121	CB7535
R1374	315-0273-00		RES., FXD, CMPSN: 27K OHM, 5%, 0.25W	01121	CB2735
R1375	315-0472-00		RES., FXD, CMPSN: 4.7K OHM, 5%, 0.25W	01121	CB4725
R1375	315-0472-00		RES., FXD, CMPSN: 4.7K OHM, 5%, 0.25W	01121	CB4725
R1401	321-0369-00		RES., FXD, FILM: 68.1K OHM, 1%, 0.125W	91637	MFF1816G68101F
R1402	321-0407-00		RES., FXD, FILM: 169K OHM, 1%, 0.125W	91637	MFF1816G16902F
R1403	321-0364-00		RES., FXD, FILM: 60.4K OHM, 1%, 0.125W	91637	MFF1816G60401F
R1404	321-0311-00		RES., FXD, FILM: 16.9K OHM, 1%, 0.125W	91637	MFF1816G16901F
R1405	321-0345-00		RES., FXD, FILM: 38.3K OHM, 1%, 0.125W	91637	MFF1816G38301F
R1408	315-0562-00		RES., FXD, CMPSN: 5.6K OHM, 5%, 0.25W	01121	CB5625
R1410	323-0265-00		RES., FXD, FILM: 5.62K OHM, 1%, 0.50W	75042	CECT0-5621F
R1412	315-0512-00		RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R1414	321-0730-06		RES., FXD, FILM: 570K OHM, 0.25%, 0.125W	91637	MFF1816G57030C
R1415	311-1225-00		RES., VAR, NONWIR: 1K OHM, 20%, 0.50W	32997	3386F-T04-102
R1416	321-0331-09		RES., FXD, FILM: 27.4K OHM, 1%, 0.125W	91637	MFF1816G27401F
R1417	315-0151-00		RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R1421	315-0104-00		RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1422	315-0821-00		RES., FXD, CMPSN: 820 OHM, 5%, 0.25W	01121	CB8215
R1424	315-0331-00		RES., FXD, CMPSN: 330 OHM, 5%, 0.25W	01121	CB3315
R1425	315-0471-00		RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1426	315-0181-00		RES., FXD, CMPSN: 180 OHM, 5%, 0.25W	01121	CB1815
R1427	315-0512-00		RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R1428	308-0365-00		RES., FXD, WW: 1.5 OHM, 5%, 3W	56289	242EX1R500JQ151
R1432	315-0432-00		RES., FXD, CMPSN: 4.3K OHM, 5%, 0.25W	01121	CB4325
R1434	304-0102-00		RES., FXD, CMPSN: 1K OHM, 10%, 1W	01121	GB1021
R1436	315-0121-00		RES., FXD, CMPSN: 120 OHM, 5%, 0.25W	01121	CB1215
R1437	315-0123-00		RES., FXD, CMPSN: 12K OHM, 5%, 0.25W	01121	CB1235
R1438	301-0182-00		RES., FXD, CMPSN: 1.8K OHM, 5%, 0.5W	01121	EB1825

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff Dscont	Name & Description	Mfr Code	Mfr Part Number
R1442	315-0203-00		RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R1444	315-0103-00		RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1445	321-0924-07		RES., FXD, FILM: 40K OHM, 0.1%, 0.125W	91637	MFF1816C40001B
R1446	321-0924-07		RES., FXD, FILM: 40K OHM, 0.1%, 0.125W	91637	MFF1816C40001B
R1447	315-0151-00		RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R1451	315-0104-00		RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1452	315-0821-00		RES., FXD, CMPSN: 820 OHM, 5%, 0.25W	01121	CB8215
R1454	315-0511-00		RES., FXD, CMPSN: 510 OHM, 5%, 0.25W	01121	CB5115
R1455	315-0471-00		RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1456	315-0181-00		RES., FXD, CMPSN: 180 OHM, 5%, 0.25W	01121	CB1815
R1457	315-0512-00		RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R1458	308-0686-00		RES., FXD, WW: 2.2 OHM, 5%, 2W	75042	BWH-2R200J
R1461	321-0332-07		RES., FXD, FILM: 28K OHM, 0.1%, 0.125W	91637	MFF1816C28001B
R1462	321-1296-07		RES., FXD, FILM: 12K OHM, 0.1%, 0.125W	91637	MFF1816C12001B
R1463	315-0152-00		RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1467	315-0123-00		RES., FXD, CMPSN: 12K OHM, 5%, 0.25W	01121	CB1235
R1468	315-0362-00		RES., FXD, CMPSN: 3.6K OHM, 5%, 0.25W	01121	CB3625
R1469	315-0822-00		RES., FXD, CMPSN: 8.2K OHM, 5%, 0.25W	01121	CB8225
R1473	315-0221-00		RES., FXD, CMPSN: 220 OHM, 5%, 0.25W	01121	CB2215
R1474	315-0433-00		RES., FXD, CMPSN: 43K OHM, 5%, 0.25W	01121	CB4335
R1475	308-0804-00		RES., FXD, WW: 0.025 OHM, 5%, 0.5W	80009	308-0804-00
R1476	315-0151-00		RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R1477	315-0432-00		RES., FXD, CMPSN: 4.3K OHM, 5%, 0.25W	01121	CB4325
R1480	321-0924-07		RES., FXD, FILM: 40K OHM, 0.1%, 0.125W	91637	MFF1816C40001B
R1481	321-1296-07		RES., FXD, FILM: 12K OHM, 0.1%, 0.125W	91637	MFF1816C12001B
R1482	315-0912-00		RES., FXD, CMPSN: 9.1K OHM, 5%, 0.25W	01121	CB9125
R1483	315-0102-00		RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1487	315-0123-00		RES., FXD, CMPSN: 12K OHM, 5%, 0.25W	01121	CB1235
R1488	315-0302-00		RES., FXD, CMPSN: 3K OHM, 5%, 0.25W	01121	CB3025
R1493	315-0221-00		RES., FXD, CMPSN: 220 OHM, 5%, 0.25W	01121	CB2215
R1494	315-0433-00		RES., FXD, CMPSN: 43K OHM, 5%, 0.25W	01121	CB4335
R1495	308-0804-00		RES., FXD, WW: 0.025 OHM, 5%, 0.5W	80009	308-0804-00
R1496	315-0151-00		RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R1497	315-0432-00		RES., FXD, CMPSN: 4.3K OHM, 5%, 0.25W	01121	CB4325
R1513	321-1713-07		RES., FXD, FILM: 36K OHM, 0.1%, 0.125W	91637	MFF1816C36001B
R1514	321-0926-07		RES., FXD, FILM: 4K OHM, 0.1%, 0.125W	91637	MFF1816C40000B
R1521	315-0512-00		RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R1526	315-0131-00		RES., FXD, CMPSN: 130 OHM, 5%, 0.25W	01121	CB1315
R1527	315-0203-00		RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R1528	315-0203-00		RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R1529	315-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1531	315-0362-00		RES., FXD, CMPSN: 3.6K OHM, 5%, 0.25W	01121	CB3625
R1532	315-0151-00		RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R1533	308-0804-00		RES., FXD, WW: 0.025 OHM, 5%, 0.5W	80009	308-0804-00
R1534	308-0804-00		RES., FXD, WW: 0.025 OHM, 5%, 0.5W	80009	308-0804-00
R1535	315-0470-00		RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R1536	315-0432-00		RES., FXD, CMPSN: 4.3K OHM, 5%, 0.25W	01121	CB4325
R1541	315-0822-00		RES., FXD, CMPSN: 8.2K OHM, 5%, 0.25W	01121	CB8225
R1542	315-0103-00		RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1543	315-0243-00		RES., FXD, CMPSN: 24K OHM, 5%, 0.25W	01121	CB2435
R1544	315-0562-00		RES., FXD, CMPSN: 5.6K OHM, 5%, 0.25W	01121	CB5625
R1545	315-0221-00		RES., FXD, CMPSN: 220 OHM, 5%, 0.25W	01121	CB2215
R1548	308-0702-00		RES., FXD, WW: 0.33 OHM, 5%, 2W	75042	BWH-R3300J

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1552	301-0561-00			RES., FXD, CMPSN: 560 OHM, 5%, 0.50W	01121	EB5615
R1556	301-0431-00			RES., FXD, CMPSN: 430 OHM, 5%, 0.50W	01121	EB4315
R1600	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R1601	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1602	321-0064-00			RES., FXD, FILM: 45.3 OHM, 1%, 0.125W	91637	MFF1816G45R30F
R1603	315-0510-04			RES., FXD, CMPSN: 51 OHM, 5%, 0.25 W	01121	CB5105
R1604	315-0330-00			RES., FXD, CMPSN: 33 OHM, 5%, 0.25W	01121	CB3305
R1605	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1606	321-0125-00			RES., FXD, FILM: 196 OHM, 1%, 0.125W	91637	MFF1816G196ROF
R1607	321-0234-00			RES., FXD, FILM: 2.67K OHM, 1%, 0.125W	91637	MFF1816G26700F
R1608	321-0225-00			RES., FXD, FILM: 2.15K OHM, 1%, 0.125W	91637	MFF1816G21500F
R1610	321-0223-00			RES., FXD, FILM: 2.05K OHM, 1%, 0.125W	91637	MFF1816G20500F
R1611	315-0151-00			RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R1612	321-0064-00			RES., FXD, FILM: 45.3 OHM, 1%, 0.125W	91637	MFF1816G45R30F
R1613	321-0196-00			RES., FXD, FILM: 1.07K OHM, 1%, 0.125W	91637	MFF1816G10700F
R1614	315-0330-00			RES., FXD, CMPSN: 33 OHM, 5%, 0.25W	01121	CB3305
R1615	321-0270-00			RES., FXD, FILM: 6.34K OHM, 1%, 0.125W	91637	MFF1816G63400F
R1616	321-0158-00			RES., FXD, FILM: 432 OHM, 1%, 0.125W	91637	MFF1816G432ROF
R1617	321-0177-00			RES., FXD, FILM: 681 OHM, 1%, 0.125W	91637	MFF1816G681ROF
R1618	315-0510-04			RES., FXD, CMPSN: 51 OHM, 5%, 0.25 W	01121	CB5105
R1619	321-0074-00			RES., FXD, FILM: 57.6 OHM, 1%, 0.125W	91637	MFF1816G57R60F
R1620	322-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.25W	91637	MFF1421G200ROF
R1621	321-0143-00			RES., FXD, FILM: 301 OHM, 1%, 0.125W	91637	MFF1816G301ROF
R1622	311-1223-00			RES., VAR, NONWIR: 250 OHM, 10%, 0.50W	32997	3386F-T04-251
R1623	315-0681-03			RES., FXD, CMPSN: 680 OHM, 5%, 0.25W	01121	CB6815
R1624	315-0181-00			RES., FXD, CMPSN: 180 OHM, 5%, 0.25W	01121	CB1815
R1625	321-0242-00			RES., FXD, FILM: 3.24K OHM, 1%, 0.125W	91637	MFF1816G32400F
R1626	311-1222-00			RES., VAR, NONWIR: 100 OHM, 20%, 0.50W	32997	3386F-T04-101
R1627	315-0271-00			RES., FXD, CMPSN: 270 OHM, 5%, 0.25W	01121	CB2715
R1628	315-0430-02			RES., FXD, CMPSN: 43 OHM, 5%, 0.25W	80009	315-0430-02
R1629	315-0103-03			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	80009	315-0103-03
R1630	315-0510-04			RES., FXD, CMPSN: 51 OHM, 5%, 0.25 W	01121	CB5105
R1632	321-0217-00			RES., FXD, FILM: 1.78K OHM, 1%, 0.125W	91637	MFF1816G17800F
R1633	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R1634	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100ROF
R1635	311-1259-00			RES., VAR, NONWIR: 100 OHM, 10%, 0.50W	32997	3329P-L58-101
R1636	321-0151-00			RES., FXD, FILM: 365 OHM, 1%, 0.125W	91637	MFF1816G365ROF
R1637	311-1221-00			RES., VAR, NONWIR: 50 OHM, 20%, 0.50W	32997	3386F-T04-500
R1638	322-0202-00			RES., FXD, FILM: 1.24K OHM, 1%, 0.25W	75042	CEBT0-1241F
R1639	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R1641	315-0103-03			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	80009	315-0103-03
R1642	315-0132-00			RES., FXD, CMPSN: 1.3K OHM, 5%, 0.25W	01121	CB1325
R1643	315-0333-00			RES., FXD, CMPSN: 33K OHM, 5%, 0.25W	01121	CB3335
R1644	322-0202-00			RES., FXD, FILM: 1.24K OHM, 1%, 0.25W	75042	CEBT0-1241F
R1645	311-1258-00			RES., VAR, NONWIR: 50 OHM, 10%, 0.50W	32997	3326P-T02-500
R1646	321-0112-00			RES., FXD, FILM: 143 OHM, 1%, 0.125W	91637	MFF1816G143ROF
R1647	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1649	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200ROF
R1651	315-0150-00			RES., FXD, CMPSN: 15 OHM, 5%, 0.25W	01121	CB1505
R1652	321-0108-00			RES., FXD, FILM: 130 OHM, 1%, 0.125W	91637	MFF1816G130ROF
R1653	301-0391-00			RES., FXD, CMPSN: 390 OHM, 5%, 0.50W	01121	EB3915
R1656	301-0271-00			RES., FXD, CMPSN: 270 OHM, 5%, 0.50W	01121	EB2715
R1657	315-0220-00			RES., FXD, CMPSN: 22 OHM, 5%, 0.25W	01121	CB2205

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff Dscnt	Name & Description	Mfr Code	Mfr Part Number
R1658	315-0471-00		RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1659	315-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1660	323-0293-00		RES., FXD, FILM: 11K OHM, 1%, 0.50W	75042	CECTO-1102F
R1662	315-0201-00		RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015
R1663	315-0390-00		RES., FXD, CMPSN: 39 OHM, 5%, 0.25W	01121	CB3905
R1664	315-0301-00		RES., FXD, CMPSN: 300 OHM, 5%, 0.25W	01121	CB3015
R1665	315-0680-00		RES., FXD, CMPSN: 68 OHM, 5%, 0.25W	01121	CB6805
R1668	315-0510-04		RES., FXD, CMPSN: 51 OHM, 5%, 0.25 W	01121	CB5105
R1670	321-0312-00		RES., FXD, FILM: 17.4K OHM, 1%, 0.125W	91637	MFF1816G17401F
R1671	315-0823-00		RES., FXD, CMPSN: 82K OHM, 5%, 0.25W	01121	CB8235
R1672	315-0272-00		RES., FXD, CMPSN: 2.7K OHM, 5%, 0.25W	01121	CB2725
R1673	315-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1674	315-0223-00		RES., FXD, CMPSN: 22K OHM, 5%, 0.25W	01121	CB2235
R1675	315-0273-00		RES., FXD, CMPSN: 27K OHM, 5%, 0.25W	01121	CB2735
R1676	315-0620-00		RES., FXD, CMPSN: 62 OHM, 5%, 0.25W	01121	CB6205
R1679	315-0430-02		RES., FXD, CMPSN: 43 OHM, 5%, 0.25W	80009	315-0430-02
R1680	315-0203-02		RES., FXD, CMPSN: 20K OHM, +/-5%, 0.25W	01121	CB2035
R1682	315-0105-03		RES., FXD, CMPSN: 1M OHM, 5%, 0.25W	01121	CB1055
R1685	315-0105-03		RES., FXD, CMPSN: 1M OHM, 5%, 0.25W	01121	CB1055
R1687	315-0104-03		RES., FXD CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1688	315-0103-03		RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	80009	315-0103-03
R1691	303-0150-00		RES., FXD, CMPSN: 15 OHM, 5%, 1W	01121	GB1505
R1692	315-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1693	323-0140-00		RES., FXD, FILM: 280 OHM, 1%, 0.50W	75042	CECTO-2800F
R1694	315-0161-02		RES., FXD, CMPSN: 160 OHM, 5%, 0.25W	01121	CB1615
R1695	321-0228-00		RES., FXD, FILM: 2.32K OHM, 1%, 0.125W	91637	MFF1816G23200F
R1696	321-0062-00		RES., FXD, FILM: 43.2 OHM, 1%, 0.125W	91637	MFF1816G43R20F
R1697	321-0204-00		RES., FXD, FILM: 1.3K OHM, 1%, 0.125W	91637	MFF1816G13000F
R1698	315-0363-00		RES., FXD, CMPSN: 36K OHM, 5%, 0.25W	01121	CB3635
R1699	323-0140-00		RES., FXD, FILM: 280 OHM, 1%, 0.50W	75042	CECTO-2800F
R1706	315-0472-00		RES., FXD, CMPSN: 4.7K OHM, 5%, 0.25W	01121	CB4725
R1708	315-0102-03		RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	80009	315-0102-03
R1709	315-0123-00		RES., FXD, CMPSN: 12K OHM, 5%, 0.25W	01121	CB1235
R1712	301-0164-00		RES., FXD, CMPSN: 160K OHM, 5%, 0.50W	01121	EB1645
R1713	321-0414-00		RES., FXD, FILM: 200K OHM, 1%, 0.125W	91637	MFF1816G20002F
R1714	321-0138-00		RES., FXD, FILM: 267 OHM, 1%, 0.125W	91637	MFF1816G267ROF
R1716	323-0793-07		RES., FXD, FILM: 2.5M OHM, 1%, 0.5W	91637	HFF129C250003B
R1717	323-0793-07		RES., FXD, FILM: 2.5M OHM, 1%, 0.5W	91637	HFF129C250003B
R1718	323-0793-07		RES., FXD, FILM: 2.5M OHM, 1%, 0.5W	91637	HFF129C250003B
R1719	321-0440-00		RES., FXD, FILM: 374K OHM, 1%, 0.125W	91637	MFF1816G374002F
R1720	311-1232-00		RES., VAR, NONWIR: 50K OHM, 20%, 0.50W	32997	3386F-T04-503
R1722	321-0318-00		RES., FXD, FILM: 20K OHM, 1%, 0.125W	91637	MFF1816G20001F
R1724	321-0254-00		RES., FXD, FILM: 4.32K OHM, 1%, 0.125W	91637	MFF1816G43200F
R1725	301-0104-00		RES., FXD, CMPSN: 100K OHM, 5%, 0.5W	01121	EB1045
R1726	301-0104-00		RES., FXD, CMPSN: 100K OHM, 5%, 0.5W	01121	EB1045
R1732	321-0280-00		RES., FXD, FILM: 8.06K OHM, 1%, 0.125W	91637	MFF1816G80600F
R1733	315-0755-00		RES., FXD, CMPSN: 7.5M OHM, 5%, 0.25W	01121	CB7555
R1734	321-0184-00		RES., FXD, FILM: 806 OHM, 1%, 0.125W	91637	MFF1816G806ROF
R1735	321-0269-00		RES., FXD, FILM: 6.19K OHM, 1%, 0.125W	91637	MFF1816G61900F
R1736	315-0566-00		RES., FXD, CMPSN: 56M OHM, 5%, 0.25W	01121	CB5665
R1738	315-0473-00		RES., FXD, CMPSN: 47K OHM, 5%, 0.25W	01121	CB4735
R1741	321-0275-00		RES., FXD, FILM: 7.15K OHM, 1%, 0.125W	91637	MFF1816G71500F
R1742	321-0353-00		RES., FXD, FILM: 46.4K OHM, 1%, 0.125W	91637	MFF1816G46401F

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff Dscont	Name & Description	Mfr Code	Mfr Part Number
R1743	315-0473-00		RES., FXD, CMPSN:47K OHM, 5%, 0.25W	01121	CB4735
R1746	311-1232-00		RES., VAR, NONWIR:50K OHM, 20%, 0.50W	32997	3386F-T04-503
R1747	315-0103-03		RES., FXD, CMPSN:10K OHM, 5%, 0.25W	80009	315-0103-03
R1748	315-0103-03		RES., FXD, CMPSN:10K OHM, 5%, 0.25W	80009	315-0103-03
R1750	301-0152-00		RES., FXD, CMPSN:1.5K OHM, 5%, 0.50W	01121	EB1525
R1754	323-0540-00		RES., FXD, FILM:4.12M OHM, 1%, 0.50W	91637	HMF129G41203F
R1755	301-0106-00		RES., FXD, CMPSN:10M OHM, 5%, 0.50W	01121	EB1065
R1756	315-0101-00		RES., FXD, CMPSN:100 OHM, 5%, 0.25W	01121	CB1015
R1757	321-0044-00		RES., FXD, FILM:28 OHM, 1%, 0.125W	91637	MFF1816G28R00F
R1758	321-0033-00		RES., FXD, FILM:21.5 OHM, 1%, 0.125W	91637	MFF1816G21R50F
R1764	301-0103-00		RES., FXD, CMPSN:10K OHM, 5%, 0.50W	01121	EB1035
R1770	315-0470-03		RES., FXD, CMPSN:47 OHM, 5%, 0.25W	01121	CB4705
R1771	315-0391-00		RES., FXD, CMPSN:390 OHM, 5%, 0.25W	01121	CB3915
R1772	315-0512-00		RES., FXD, CMPSN:5.1K OHM, 5%, 0.25W	01121	CB5125
R1774	307-0104-00		RES., FXD, CMPSN:3.3 OHM, 5%, 0.25W	01121	CB33G5
R1776	315-0101-00		RES., FXD, CMPSN:100 OHM, 5%, 0.25W	01121	CB1015
R1778	315-0472-00		RES., FXD, CMPSN:4.7K OHM, 5%, 0.25W	01121	CB4725
R1783	315-0331-00		RES., FXD, CMPSN:330 OHM, 5%, 0.25W	01121	CB3315
R1784	315-0102-03		RES., FXD, CMPSN:1K OHM, 5%, 0.25W	80009	315-0102-03
R1785	315-0332-00		RES., FXD, CMPSN:3.3K OHM, 5%, 0.25W	01121	CB3325
R1788	301-0105-00		RES., FXD, CMPSN:1M OHM, 5%, 0.50W	01121	EB1055
R1789	301-0105-00		RES., FXD, CMPSN:1M OHM, 5%, 0.50W	01121	EB1055
R1790	315-0104-03		RES., FXD CMPSN:100K OHM, 5%, 0.25W	01121	CB1045
R1791	315-0151-00		RES., FXD, CMPSN:150 OHM, 5%, 0.25W	01121	CB1515
R1792	315-0103-03		RES., FXD, CMPSN:10K OHM, 5%, 0.25W	80009	315-0103-03
R1793	315-0151-00		RES., FXD, CMPSN:150 OHM, 5%, 0.25W	01121	CB1515
R1794	315-0183-03		RES., FXD, CMPSN:18K OHM, 5%, 0.25W	01121	CB1835
R1795	315-0226-01		RES., FXD, CMPSN:22M OHM, 5%, 0.25W	01121	CB2265
R1796	321-0193-00		RES., FXD, FILM:1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R1797	321-0319-00		RES., FXD, FILM:20.5K OHM, 1%, 0.125W	91637	MFF1816G20501F
R1800	315-0683-03		RES., FXD, CMPSN:68K OHM, 5%, 0.25W	01121	CB6835
R1802A-C	307-0556-00		RES NTWK, FXD FI:HIGH VOLTAGE DIVIDER	80009	307-0556-00
R1803	315-0204-00		RES., FXD, CMPSN:200K OHM, 5%, 0.25W	01121	CB2045
R1804	315-0755-00		RES., FXD, CMPSN:7.5M OHM, 5%, 0.25W	01121	CB7555
R1805	311-1235-00		RES., VAR, NONWIR:100K OHM, 20%, 0.50W	32997	3386F-T04-104
R1806	321-0983-00		RES., FXD, FILM:4.5M OHM, 1%, 0.125W	91637	HMF188G45003F
R1807	315-0302-00		RES., FXD, CMPSN:3K OHM, 5%, 0.25W	01121	CB3025
R1811	301-0155-00		RES., FXD, CMPSN:1.5M OHM, 5%, 0.50W	01121	EB1555
R1812	301-0155-00		RES., FXD, CMPSN:1.5M OHM, 5%, 0.50W	01121	EB1555
R1813	301-0205-00		RES., FXD, CMPSN:2M OHM, 5%, 0.50W	01121	EB2055
R1814	301-0205-00		RES., FXD, CMPSN:2M OHM, 5%, 0.50W	01121	EB2055
R1815	315-0226-01		RES., FXD, CMPSN:22M OHM, 5%, 0.25W	01121	CB2265
R1816	315-0103-03		RES., FXD, CMPSN:10K OHM, 5%, 0.25W	80009	315-0103-03
R1817	315-0104-03		RES., FXD CMPSN:100K OHM, 5%, 0.25W	01121	CB1045
R1818	315-0183-03		RES., FXD, CMPSN:18K OHM, 5%, 0.25W	01121	CB1835
R1819	315-0183-03		RES., FXD, CMPSN:18K OHM, 5%, 0.25W	01121	CB1835
R1820	315-0103-03		RES., FXD, CMPSN:10K OHM, 5%, 0.25W	80009	315-0103-03
R1821	315-0105-03		RES., FXD, CMPSN:1M OHM, 5%, 0.25W	01121	CB1055
R1822	323-0540-00		RES., FXD, FILM:4.12M OHM, 1%, 0.50W	91637	HMF129G41203F
R1823	323-0540-00		RES., FXD, FILM:4.12M OHM, 1%, 0.50W	91637	HMF129G41203F
R1824	323-0540-00		RES., FXD, FILM:4.12M OHM, 1%, 0.50W	91637	HMF129G41203F
R1825	311-1967-00		RES., VAR, NONWIR:PNL, 2M OHM, 10%, 0.50W	12697	CM41753
R1827	323-0540-00		RES., FXD, FILM:4.12M OHM, 1%, 0.50W	91637	HMF129G41203F

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1828	323-0525-00			RES., FXD, FILM: 2.87M OHM, 1%, 0.5W	03888	PME65
R1829	323-0540-00			RES., FXD, FILM: 4.12M OHM, 1%, 0.50W	91637	HMF129G41203F
R1831	315-0102-03			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	80009	315-0102-03
R1834	315-0103-03			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	80009	315-0103-03
R1835	315-0153-03			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R1837	315-0105-03			RES., FXD, CMPSN: 1M OHM, 5%, 0.25W	01121	CB1055
R1838	315-0153-03			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R1839	321-0444-00			RES., FXD, FILM: 412K OHM, 1%, 0.125W	91637	MFF1816G41202F
R1840	321-0486-00			RES., FXD, FILM: 1.13M OHM, 1%, 0.125W	91637	HMF188G11303F
R1841	315-0184-01			RES., FXD, CMPSN: 180K OHM, +/-5%, 0.25W	80009	315-0184-01
R1842	315-0103-03			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	80009	315-0103-03
R1848	315-0683-03			RES., FXD, CMPSN: 68K OHM, 5%, 0.25W	01121	CB6835
R1849	315-0161-02			RES., FXD, CMPSN: 160 OHM, 5%, 0.25W	01121	CB1615
R1850	315-0161-02			RES., FXD, CMPSN: 160 OHM, 5%, 0.25W	01121	CB1615
R1852	315-0161-02			RES., FXD, CMPSN: 160 OHM, 5%, 0.25W	01121	CB1615
R1853	311-1969-00			RES., VAR, NONWIR: PNL, DUAL, 5M OHM, 20%, 0.50W	01121	72P4N048S505M
R1854	311-1969-00			RES., VAR, NONWIR: PNL, DUAL, 5M OHM, 20%, 0.50W	01121	72P4N048S505M
R1855	311-1969-00			RES., VAR, NONWIR: PNL, DUAL, 5M OHM, 20%, 0.50W	01121	72P4N048S505M
R1856	311-1969-00			RES., VAR, NONWIR: PNL, DUAL, 5M OHM, 20%, 0.50W	01121	72P4N048S505M
R1857	323-0505-00			RES., FXD, FILM: 1.78M OHM, 1%, 0.50W	91637	MFF1226G17803F
R1858	323-0505-00			RES., FXD, FILM: 1.78M OHM, 1%, 0.50W	91637	MFF1226G17803F
R1859	323-0505-00			RES., FXD, FILM: 1.78M OHM, 1%, 0.50W	91637	MFF1226G17803F
R1860	315-0161-02			RES., FXD, CMPSN: 160 OHM, 5%, 0.25W	01121	CB1615
R1862	315-0161-02			RES., FXD, CMPSN: 160 OHM, 5%, 0.25W	01121	CB1615
R1863	311-1969-00			RES., VAR, NONWIR: PNL, DUAL, 5M OHM, 20%, 0.50W	01121	72P4N048S505M
R1864	311-1969-00			RES., VAR, NONWIR: PNL, DUAL, 5M OHM, 20%, 0.50W	01121	72P4N048S505M
R1865	311-1969-00			RES., VAR, NONWIR: PNL, DUAL, 5M OHM, 20%, 0.50W	01121	72P4N048S505M
R1866	311-1969-00			RES., VAR, NONWIR: PNL, DUAL, 5M OHM, 20%, 0.50W	01121	72P4N048S505M
R1867	323-0505-00			RES., FXD, FILM: 1.78M OHM, 1%, 0.50W	91637	MFF1226G17803F
R1870	315-0161-02			RES., FXD, CMPSN: 160 OHM, 5%, 0.25W	01121	CB1615
R1872	315-0161-02			RES., FXD, CMPSN: 160 OHM, 5%, 0.25W	01121	CB1615
R1873	311-1969-00			RES., VAR, NONWIR: PNL, DUAL, 5M OHM, 20%, 0.50W	01121	72P4N048S505M
R1874	311-1969-00			RES., VAR, NONWIR: PNL, DUAL, 5M OHM, 20%, 0.50W	01121	72P4N048S505M
R1875	311-1969-00			RES., VAR, NONWIR: PNL, DUAL, 5M OHM, 20%, 0.50W	01121	72P4N048S505M
R1876	311-1969-00			RES., VAR, NONWIR: PNL, DUAL, 5M OHM, 20%, 0.50W	01121	72P4N048S505M
R1877	315-0103-03			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	80009	315-0103-03
R1880	315-0161-02			RES., FXD, CMPSN: 160 OHM, 5%, 0.25W	01121	CB1615
R1881	315-0361-00			RES., FXD, CMPSN: 360 OHM, 5%, 0.25W	01121	CB3615
R1882	323-0540-00			RES., FXD, FILM: 4.12M OHM, 1%, 0.50W	91637	HMF129G41203F
R1883	311-1968-00			RES., VAR, NONWIR: PNL, 5M OHM, 20%, 0.50W	01121	72M4N048S505M
R1884	323-0745-00			RES., FXD, FILM: 5M OHM, 1%, 0.50W	91637	MFF1226G50003F
R1885	323-0745-00			RES., FXD, FILM: 5M OHM, 1%, 0.50W	91637	MFF1226G50003F
R1886	323-0745-00			RES., FXD, FILM: 5M OHM, 1%, 0.50W	91637	MFF1226G50003F
R1887	323-0496-00			RES., FXD, FILM: 1.43M OHM, 1%, 0.50W	91637	MFF1226G14303F
R1888	311-1227-00			RES., VAR, NONWIR: 5K OHM, 20%, 0.50W	32997	3386F-T04-502
R1890	315-0151-00			RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R1891	311-1232-00			RES., VAR, NONWIR: 50K OHM, 20%, 0.50W	32997	3386F-T04-503
R1893	315-0151-00			RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R1894	311-1235-00			RES., VAR, NONWIR: 100K OHM, 20%, 0.50W	32997	3386F-T04-104
R1895	315-0151-00			RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R1896	321-0277-00			RES., FXD, FILM: 7.5K OHM, 1%, 0.125W	91637	MFF1816G75000F
R1897	321-0314-00			RES., FXD, FILM: 18.2K OHM, 1%, 0.125W	91637	MFF1816G18201F
R1900	311-1587-00			RES., VAR, NONWIR: 10K OHM, 20%, 1W	01121	12M435

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1901	315-0106-00			RES., FXD, CMPSN: 10M OHM, 5%, 0.25W	01121	CB1065
R1902	311-1319-00			RES., VAR, NONWIR: 10K OHM, 10%, 0.75W	01121	4SP103
R1903	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1905	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1906	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1908	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R1909	315-0244-00			RES., FXD, CMPSN: 240K OHM, 5%, 0.25W	01121	CB2445
R1910	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1911	321-0143-00			RES., FXD, FILM: 301 OHM, 1%, 0.125W	91637	MFF1816G301ROF
R1915	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1916	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R1917	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R1918	315-0106-00			RES., FXD, CMPSN: 10M OHM, 5%, 0.25W	01121	CB1065
R1919	315-0105-00			RES., FXD, CMPSN: 1M OHM, 5%, 0.25W	01121	CB1055
R1920	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1921	315-0105-00			RES., FXD, CMPSN: 1M OHM, 5%, 0.25W	01121	CB1055
R1922	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R1923	311-1339-00			RES., VAR, NONWIR: 5K OHM, 10%, 0.50W	02111	43P502
R1924	311-1588-00			RES., VAR, NONWIR: 5K OHM, 20%, 1W	01121	12M299
R1925	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R1926	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1927	321-0226-00			RES., FXD, FILM: 2.21K OHM, 1%, 0.125W	91637	MFF1816G22100F
R1928	321-0180-00			RES., FXD, FILM: 732 OHM, 1%, 0.125W	91637	MFF1816G732ROF
R1929	321-0190-00			RES., FXD, FILM: 931 OHM, 1%, 0.125W	91637	MFF1816G931ROF
R1930	315-0431-00			RES., FXD, CMPSN: 430 OHM, 5%, 0.25W	01121	CB4315
R1931	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R1932	323-0189-00			RES., FXD, FILM: 909 OHM, 1%, 0.50W	75042	CECT0-9090F
R1933	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1934	315-0301-00			RES., FXD, CMPSN: 300 OHM, 5%, 0.25W	01121	CB3015
R1935	315-0473-00			RES., FXD, CMPSN: 47K OHM, 5%, 0.25W	01121	CB4735
R1936	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1936	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1937	315-0123-00			RES., FXD, CMPSN: 12K OHM, 5%, 0.25W	01121	CB1235
R1938	315-0331-00			RES., FXD, CMPSN: 330 OHM, 5%, 0.25W	01121	CB3315
R1940	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R1941	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R1942	315-0204-00			RES., FXD, CMPSN: 200K OHM, 5%, 0.25W	01121	CB2045
R1943	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100ROF
R1944	321-0262-00			RES., FXD, FILM: 5.23K OHM, 1%, 0.125W	91637	MFF1816G52300F
R1945	301-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.50W	01121	EB1025
R1946	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100ROF
R1948	321-0190-00			RES., FXD, FILM: 931 OHM, 1%, 0.125W	91637	MFF1816G931ROF
R1950	315-0393-00			RES., FXD, CMPSN: 39K OHM, 5%, 0.25W	01121	CB3935
R1951	321-0481-00			RES., FXD, FILM: 1M OHM, 1%, 0.125W	91637	MFF1816G10003F
R1952	321-0300-00			RES., FXD, FILM: 13K OHM, 1%, 0.125W	91637	MFF1816G13001F
R1953	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1954	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1955	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1956	315-0223-00			RES., FXD, CMPSN: 22K OHM, 5%, 0.25W	01121	CB2235
R1957	315-0821-00			RES., FXD, CMPSN: 820 OHM, 5%, 0.25W	01121	CB8215
R1958	315-0625-00			RES., FXD, CMPSN: 6.2M OHM, 5%, 0.25W	01121	CB6255
R1959	321-0217-00			RES., FXD, FILM: 1.78K OHM, 1%, 0.125W	91637	MFF1816G17800F
R1960	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200ROF

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1961	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1962	315-0514-00			RES., FXD, CMPSN: 510K OHM, 5%, 0.25W	01121	CB5145
R1963	321-0283-00			RES., FXD, FILM: 8.66K OHM, 1%, 0.125W	91637	MFF1816G86600F
R1964	321-0205-00			RES., FXD, FILM: 1.33K OHM, 1%, 0.125W	91637	MFF1816G13300F
R1965	321-0260-00			RES., FXD, FILM: 4.99K OHM, 1%, 0.125W	91637	MFF1816G49900F
R1966	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1967	315-0473-00			RES., FXD, CMPSN: 47K OHM, 5%, 0.25W	01121	CB4735
R1968	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1969	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1970	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1971	315-0625-00			RES., FXD, CMPSN: 6.2M OHM, 5%, 0.25W	01121	CB6255
R1972	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1973	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1974	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1975	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R1976	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1977	315-0433-00			RES., FXD, CMPSN: 43K OHM, 5%, 0.25W	01121	CB4335
R1979	321-0296-00			RES., FXD, FILM: 11.8K OHM, 1%, 0.125W	91637	MFF1816G11801F
R1980	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1981	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1982	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1983	321-0243-00			RES., FXD, FILM: 3.32K OHM, 1%, 0.125W	91637	MFF1816G33200F
R1985	315-0154-00			RES., FXD, CMPSN: 150K OHM, 5%, 0.25W	01121	CB1545
R1986	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1987	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1988	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1989	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1990	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1991	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1992	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1993	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1994	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1995	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1996	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1997	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1998	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R1999	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R2005	311-1372-00			RES., VAR, NONWIR: 100K OHM, 20%, 1W	01121	73M1G040L104M
R2007	315-0622-00			RES., FXD, CMPSN: 6.2K OHM, 5%, 0.25W	01121	CB6225
R2008	315-0303-00			RES., FXD, CMPSN: 30K OHM, 5%, 0.25W	01121	CB3035
R2009	321-0193-00			RES., FXDFILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R2146	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R2010	311-1375-00			RES., VAR, NONWIR: 10K OHM, 20%, 1W	01121	73M1G040L103M
R2015	311-1372-00			RES., VAR, NONWIR: 100K OHM, 20%, 1W	01121	73M1G040L104M
R2016	315-0154-00			RES., FXD, CMPSN: 150K OHM, 5%, 0.25W	01121	CB1545
R2017	315-0622-00			RES., FXD, CMPSN: 6.2K OHM, 5%, 0.25W	01121	CB6225
R2018	315-0303-00			RES., FXD, CMPSN: 30K OHM, 5%, 0.25W	01121	CB3035
R2019	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R2020	311-1375-00			RES., VAR, NONWIR: 10K OHM, 20%, 1W	01121	73M1G040L103M
R2025	311-1973-00			RES., VAR, NONWIR: PNL, 2.5M OHM, 20%, 0.75W	01121	73M1G040L255M
R2035	311-1972-00			RES., VAR, NONWIR: PNL, 2K OHM, 10%, 2.0 W	01121	70N1G100L202W
R2101	315-0682-00			RES., FXD, CMPSN: 6.8K OHM, 5%, 0.25W	01121	CB6825
R2102	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R2104	315-0333-00			RES., FXD, CMPSN: 33K OHM, 5%, 0.25W	01121	CB3335
R2105	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R2107	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R2108	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R2109	315-0221-00			RES., FXD, CMPSN: 220 OHM, 5%, 0.25W	01121	CB2215
R2112	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R2113	315-0301-00			RES., FXD, CMPSN: 300 OHM, 5%, 0.25W	01121	CB3015
R2122	315-0432-00			RES., FXD, CMPSN: 4.3K OHM, 5%, 0.25W	01121	CB4325
R2123	315-0683-00			RES., FXD, CMPSN: 68K OHM, 5%, 0.25W	01121	CB6835
R2127	315-0302-00			RES., FXD, CMPSN: 3K OHM, 5%, 0.25W	01121	CB3025
R2128	311-1263-00			RES., VAR, NONWIR: 1K OHM, 10%, 0.50W	32997	3329P-L58-102
R2129	315-0183-00			RES., FXD, CMPSN: 18K OHM, 5%, 0.25W	01121	CB1835
R2135	315-0393-00			RES., FXD, CMPSN: 39K OHM, 5%, 0.25W	01121	CB3935
R2137	315-0752-00			RES., FXD, CMPSN: 7.5K OHM, 5%, 0.25W	01121	CB7525
R2139	315-0242-00			RES., FXD, CMPSN: 2.4K OHM, 5%, 0.25W	01121	CB2425
R2144	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R2146	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R2148	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R2150	321-0403-00			RES., FXD, FILM: 154K OHM, 1%, 0.125W	91637	MFF1816G15402F
R2151	321-0372-00			RES., FXD, FILM: 73.2K OHM, 1%, 0.125W	91637	MFF1816G73201F
R2153	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R2155	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R2158	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R2161	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R2162	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R2163	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R2165	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R2166	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R2167	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R2169	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R2170	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R2171	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R2173	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R2174	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R2175	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R2177	315-0511-00			RES., FXD, CMPSN: 510 OHM, 5%, 0.25W	01121	CB5115
R2178	315-0511-00			RES., FXD, CMPSN: 510 OHM, 5%, 0.25W	01121	CB5115
R2179	315-0511-00			RES., FXD, CMPSN: 510 OHM, 5%, 0.25W	01121	CB5115
R2182	321-0262-00			RES., FXD, FILM: 5.23K OHM, 1%, 0.125W	91637	MFF1816G52300F
R2183	311-1224-00			RES., VAR, NONWIR: 500 OHM, 20%, 0.50W	32997	3386F-T04-501
R2191	315-0513-00			RES., FXD, CMPSN: 51K OHM, 5%, 0.25W	01121	CB5135
R2192	315-0133-00			RES., FXD, CMPSN: 13K OHM, 5%, 0.25W	01121	CB1335
R2193	315-0133-00			RES., FXD, CMPSN: 13K OHM, 5%, 0.25W	01121	CB1335
R2194	315-0753-00			RES., FXD, CMPSN: 75K OHM, 5%, 0.25W	01121	CB7535
R2196	321-0308-00			RES., FXD, FILM: 15.8K OHM, 1%, 0.125W	91637	MFF1816G15801F
R2197	315-0513-00			RES., FXD, CMPSN: 51K OHM, 5%, 0.25W	01121	CB5135
R2198	321-0319-00			RES., FXD, FILM: 20.5K OHM, 1%, 0.125W	91637	MFF1816G20501F
R2199	321-0335-00			RES., FXD, FILM: 30.1K OHM, 1%, 0.125W	91637	MFF1816G30101F
R2201	315-0154-00			RES., FXD, CMPSN: 150K OHM, 5%, 0.25W	01121	CB1545
R2202	321-0335-00			RES., FXD, FILM: 30.1K OHM, 1%, 0.125W	91637	MFF1816G30101F
R2203	321-0344-00			RES., FXD, FILM: 37.4K OHM, 1%, 0.125W	91637	MFF1816G37401F
R2204	321-0335-00			RES., FXD, FILM: 30.1K OHM, 1%, 0.125W	91637	MFF1816G30101F
R2206	315-0513-00			RES., FXD, CMPSN: 51K OHM, 5%, 0.25W	01121	CB5135

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R2207	315-0154-00			RES., FXD, CMPSN: 150K OHM, 5%, 0.25W	01121	CB1545
R2208	321-0335-00			RES., FXD, FILM: 30.1K OHM, 1%, 0.125W	91637	MFF1816G30101F
R2209	321-0335-00			RES., FXD, FILM: 30.1K OHM, 1%, 0.125W	91637	MFF1816G30101F
R2211	315-0752-00			RES., FXD, CMPSN: 7.5K OHM, 5%, 0.25W	01121	CB7525
R2213	321-0259-00			RES., FXD, FILM: 4.87K OHM, 1%, 0.125W	91637	MFF1816G48700F
R2214	311-1224-00			RES., VAR, NONWIR: 500 OHM, 20%, 0.50W	32997	3386F-T04-501
R2215	315-0133-00			RES., FXD, CMPSN: 13K OHM, 5%, 0.25W	01121	CB1335
R2217	315-0124-00			RES., FXD, CMPSN: 120K OHM, 5%, 0.25W	01121	CB1245
R2219	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R2220	321-0299-00			RES., FXD, FILM: 12.7K OHM, 1%, 0.125W	91637	MFF1816G12701F
R2221	321-0212-00			RES., FXD, FILM: 1.58K OHM, 1%, 0.125W	91637	MFF1816G15800F
R2226	315-0222-00			RES., FXD, CMPSN: 2.2K OHM, 5%, 0.25W	01121	CB2225
R2227	321-0268-00			RES., FXD, FILM: 6.04K OHM, 1%, 0.125W	91637	MFF1816G60400F
R2229	321-0210-00			RES., FXD, FILM: 1.5K OHM, 1%, 0.125W	91637	MFF1816G15000F
R2231	315-0303-00			RES., FXD, CMPSN: 30K OHM, 5%, 0.25W	01121	CB3035
R2235	315-0203-00			RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R2236	315-0203-00			RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R2237	315-0203-00			RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R2238	315-0203-00			RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R2241	321-0326-00			RES., FXD, FILM: 24.3K OHM, 1%, 0.125W	91637	MFF1816G24301F
R2251	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R2252	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R2253	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R2254	315-0303-00			RES., FXD, CMPSN: 30K OHM, 5%, 0.25W	01121	CB3035
R2261	315-0272-00			RES., FXD, CMPSN: 2.7K OHM, 5%, 0.25W	01121	CB2725
R2262	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R2265	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R2266	315-0912-00			RES., FXD, CMPSN: 9.1K OHM, 5%, 0.25W	01121	CB9125
R2268	321-0296-00			RES., FXD, FILM: 11.8K OHM, 1%, 0.125W	91637	MFF1816G11801F
R2273	311-1226-00			RES., VAR, NONWIR: 2.5K OHM, 20%, 0.50W	32997	3386F-T04-252
R2274	321-0153-00			RES., FXD, FILM: 383 OHM, 1%, 0.125W	91637	MFF1816G383R0F
R2275	321-0170-00			RES., FXD, FILM: 576 OHM, 1%, 0.125W	91637	MFF1816G576R0F
R2276	315-0223-00			RES., FXD, CMPSN: 22K OHM, 5%, 0.25W	01121	CB2235
R2277	321-0250-00			RES., FXD, FILM: 3.92K OHM, 1%, 0.125W	91637	MFF1816G39200F
R2278	315-0823-00			RES., FXD, CMPSN: 82K OHM, 5%, 0.25W	01121	CB8235
R2279	321-0222-00			RES., FXD, FILM: 2K OHM, 1%, 0.125W	91637	MFF1816G20000F
R2280	315-0823-00			RES., FXD, CMPSN: 82K OHM, 5%, 0.25W	01121	CB8235
R2281	315-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R2282	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R2283	315-0753-00			RES., FXD, CMPSN: 75K OHM, 5%, 0.25W	01121	CB7535
R2284	321-0216-00			RES., FXD, FILM: 1.74K OHM, 1%, 0.125W	91637	MFF1816G17400F
R2285	321-0245-00			RES., FXD, FILM: 3.48K OHM, 1%, 0.125W	91637	MFF1816G34800F
R2286	321-0209-00			RES., FXD, FILM: 1.47K OHM, 1%, 0.125W	91637	MFF1816G14700F
R2287	321-0199-00			RES., FXD, FILM: 1.15K OHM, 1%, 0.125W	91637	MFF1816G11500F
R2288	321-0273-00			RES., FXD, FILM: 6.81K OHM, 1%, 0.125W	91637	MFF1816G68100F
R2289	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R2291	311-1225-00			RES., VAR, NONWIR: 1K OHM, 20%, 0.50W	32997	3386F-T04-102
R2292	315-0132-00			RES., FXD, CMPSN: 1.3K OHM, 5%, 0.25W	01121	CB1325
R2293	321-0245-00			RES., FXD, FILM: 3.48K OHM, 1%, 0.125W	91637	MFF1816G34800F
R2294	321-0255-00			RES., FXD, FILM: 4.42K OHM, 1%, 0.125W	91637	MFF1816G44200F
R2295	321-0241-00			RES., FXD, FILM: 3.16K OHM, 1%, 0.125W	91637	MFF1816G31600F
R2297	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R2298	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R2299	315-0431-00			RES., FXD, CMPSN: 430 OHM, 5%, 0.25W	01121	CB4315
R4302	315-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R4304	315-0223-00			RES., FXD, CMPSN: 22K OHM, 5%, 0.25W	01121	CB2235
R4305	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R4306	315-0223-00			RES., FXD, CMPSN: 22K OHM, 5%, 0.25W	01121	CB2235
R4307	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R4312	321-0147-00			RES., FXD, FILM: 332 OHM, 1%, 0.125W	91637	MFF1816G332ROF
R4313	321-0239-00			RES., FXD, FILM: 3.01K OHM, 1%, 0.125W	91637	MFF1816G30100F
R4314	315-0912-00			RES., FXD, CMPSN: 9.1K OHM, 5%, 0.25W	01121	CB9125
R4315	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R4316	315-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015
R4318	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R4319	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R4322	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R4327	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R4333	315-0682-00			RES., FXD, CMPSN: 6.8K OHM, 5%, 0.25W	01121	CB6825
R4334	315-0303-00			RES., FXD, CMPSN: 30K OHM, 5%, 0.25W	01121	CB3035
R4335	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R4336	315-0752-00			RES., FXD, CMPSN: 7.5K OHM, 5%, 0.25W	01121	CB7525
R4342	315-0271-00			RES., FXD, CMPSN: 270 OHM, 5%, 0.25W	01121	CB2715
R4343	315-0222-00			RES., FXD, CMPSN: 2.2K OHM, 5%, 0.25W	01121	CB2225
R4344	315-0271-00			RES., FXD, CMPSN: 270 OHM, 5%, 0.25W	01121	CB2715
R4345	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R4354	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R4356	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R4357	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R4358	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R4363	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R4366	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R4367	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R4369	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R4374	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R4380	315-0302-00			RES., FXD, CMPSN: 3K OHM, 5%, 0.25W	01121	CB3025
R4381	315-0303-00			RES., FXD, CMPSN: 30K OHM, 5%, 0.25W	01121	CB3035
R4382	315-0182-00			RES., FXD, CMPSN: 1.8K OHM, 5%, 0.25W	01121	CB1825
R4390	315-0301-00			RES., FXD, CMPSN: 300 OHM, 5%, 0.25W	01121	CB3015
R4391	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R4392	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R4394	315-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R4413	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R4422	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R4423	315-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015
R4424	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R4425	315-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015
R4431	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R4432	315-0222-00			RES., FXD, CMPSN: 2.2K OHM, 5%, 0.25W	01121	CB2225
R4437	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R4438	315-0821-00			RES., FXD, CMPSN: 820 OHM, 5%, 0.25W	01121	CB8215
R4441	315-0822-00			RES., FXD, CMPSN: 8.2K OHM, 5%, 0.25W	01121	CB8225
R4442	315-0132-00			RES., FXD, CMPSN: 1.3K OHM, 5%, 0.25W	01121	CB1325
R4448	315-0271-00			RES., FXD, CMPSN: 270 OHM, 5%, 0.25W	01121	CB2715
R4449	315-0302-00			RES., FXD, CMPSN: 3K OHM, 5%, 0.25W	01121	CB3025
R4456	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R4461	321-0290-00			RES., FXD, FILM: 10.2K OHM, 1%, 0.125W	91637	MFF1816G10201F
R4462	321-0246-00			RES., FXD, FILM: 3.57K OHM, 1%, 0.125W	91637	MFF1816G35700F
R4467	321-0290-00			RES., FXD, FILM: 10.2K OHM, 1%, 0.125W	91637	MFF1816G10201F
R4468	321-0246-00			RES., FXD, FILM: 3.57K OHM, 1%, 0.125W	91637	MFF1816G35700F
R4470	315-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R4471	321-0243-00			RES., FXD, FILM: 3.32K OHM, 1%, 0.125W	91637	MFF1816G33200F
R4472	315-0242-00			RES., FXD, CMPSN: 2.4K OHM, 5%, 0.25W	01121	CB2425
R4473	315-0622-00			RES., FXD, CMPSN: 6.2K OHM, 5%, 0.25W	01121	CB6225
R4474	315-0622-00			RES., FXD, CMPSN: 6.2K OHM, 5%, 0.25W	01121	CB6225
R4475	315-0151-00			RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R4476	321-0243-00			RES., FXD, FILM: 3.32K OHM, 1%, 0.125W	91637	MFF1816G33200F
R4477	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R4478	321-0205-00			RES., FXD, FILM: 1.33K OHM, 1%, 0.125W	91637	MFF1816G13300F
R4480	315-0511-00			RES., FXD, CMPSN: 51.0 OHM, 5%, 0.25W	01121	CB5115
R4481	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R4482	321-0222-00			RES., FXD, FILM: 2K OHM, 1%, 0.125W	91637	MFF1816G20000F
R4483	321-0222-00			RES., FXD, FILM: 2K OHM, 1%, 0.125W	91637	MFF1816G20000F
R4484	315-0913-00			RES., FXD, CMPSN: 91K OHM, 5%, 0.25W	01121	CB9135
R4485	315-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015
R4486	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R4487	315-0203-00			RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R4488	315-0752-00			RES., FXD, CMPSN: 7.5K OHM, 5%, 0.25W	01121	CB7525
R4489	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R4490	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R4491	315-0203-00			RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R4492	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R4493	315-0431-00			RES., FXD, CMPSN: 430 OHM, 5%, 0.25W	01121	CB4315
R4494	315-0911-00			RES., FXD, CMPSN: 910 OHM, 5%, 0.25W	01121	CB9115
R4496	315-0431-00			RES., FXD, CMPSN: 430 OHM, 5%, 0.25W	01121	CB4315
R4498	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R4501	321-0385-00			RES., FXD, FILM: 100K OHM, 1%, 0.125W	91637	MFF1816G10002F
R4502	321-0357-00			RES., FXD, FILM: 51.1K OHM, 1%, 0.125W	91637	MFF1816G51101F
R4503	321-0385-00			RES., FXD, FILM: 100K OHM, 1%, 0.125W	91637	MFF1816G10002F
R4504	321-0238-00			RES., FXD, FILM: 2.94K OHM, 1%, 0.125W	91637	MFF1816G29400F
R4505	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R4506	321-0281-00			RES., FXD, FILM: 8.25K OHM, 1%, 0.125W	91637	MFF1816G82500F
R4507	321-0254-00			RES., FXD, FILM: 4.32K OHM, 1%, 0.125W	91637	MFF1816G43200F
R4508	321-0363-00			RES., FXD, FILM: 59K OHM, 1%, 0.125W	91637	MFF1816G59001F
R4509	321-0387-00			RES., FXD, FILM: 105K OHM, 1%, 0.125W	91637	MFF1816G10502F
RT813	307-0127-00			RES., THERMAL: 1K OHM, 10%	50157	2D1596
RT1080	307-0181-00			RES., THERMAL: 100K OHM, 10%, 4MW/DEG C	15454	1DE104-K-220EC
RT1209	307-0353-00			RES., THERMAL: 5 OHM, 10%	15454	50A5R0-K270SS-SI
RT1213	307-0353-00			RES., THERMAL: 5 OHM, 10%	15454	50A5R0-K270SS-SI
RT1696	307-0124-00			RES., THERMAL: 5K OHM, 10%	50157	1D1618
RT1804	307-0181-00			RES., THERMAL: 100K OHM, 10%, 4MW/DEG C	15454	1DE104-K-220EC
S70	260-0638-00			SW, THERMOSTATIC: 10A, 240V, OPEN 75 DEG C	93410	110-364
S315	263-0021-02			SWITCH, PB ASSY: 4 LATCH, 7.5MM, 8 CONTACTS	80009	263-0021-02
S325	263-0022-02			SWITCH, PB ASSY: 5 LATCH, 7.5MM, 6 CONTACTS	80009	263-0022-02
S345	263-0013-10			SWITCH, PB ASSY: 3 LATCH, 10MM, W/3 CONTACTS	80009	263-0013-10
S365	263-0013-10			SWITCH, PB ASSY: 3 LATCH, 10MM, W/3 CONTACTS	80009	263-0013-10
S395	263-0013-11			SWITCH, PB ASSY: 3 LATCH, 10MM, 5 CONTACTS	80009	263-0013-11
S1200	260-1709-00			SWITCH, PUSH: POWER	77342	A9M1-762-6-3

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
S1212	260-0450-00			SWITCH, SLIDE: 3 POS, DOUBLE POLE	82389	11D-1007
S1540	260-1300-00			SWITCH, SLIDE: DPDT, 3A, 125V	82389	46206LFE
S1900	311-1587-00			RES., VAR, NONWIR: 10K OHM, 20%, 1W	01121	12M435
S1905	260-1380-00			SWITCH, PUSH: 2 STATION, NON SHORT, INTLK	80009	260-1380-00
S1910	260-1380-00			SWITCH, PUSH: 2 STATION, NON SHORT, INTLK	80009	260-1380-00
S1915	260-1380-00			SWITCH, PUSH: 2 STATION, NON SHORT, INTLK	80009	260-1380-00
S1920	260-1380-00			SWITCH, PUSH: 2 STATION, NON SHORT, INTLK	80009	260-1380-00
S1924	311-1588-00			RES., VAR, NONWIR: 5K OHM, 20%, 1W	01121	12M299
S1930	260-1208-00			SWITCH, PUSH: DPDT	80009	260-1208-00
S1940	260-1208-00			SWITCH, PUSH: DPDT	80009	260-1208-00
S1988	260-0247-00			SWITCH, PUSH: SPST, 1A, 115VAC	81073	30YY1009
S2005	260-1208-00			SWITCH, PUSH: DPDT	80009	260-1208-00
S2110	260-0723-00			SWITCH, SLIDE: DPDT, 0.5A, 125VAC	79727	GF126-0028
S4488	260-1811-00			SWITCH, SLIDE: DPDT, 0.5A, 125VAC DC	82389	C56206L2
T1208	120-0636-00			XFMR, PWR, STPDN: PRI 2.625V, SEC 1V, 0.005A	80009	120-0636-00
T1225	120-0743-00			XFMR, TOROID: 13 TURNS, BIFILAR	80009	120-0743-00
T1230	120-0744-00			XFMR, TOROID: 5 WINDINGS	80009	120-0744-00
T1235	120-0747-00			XFMR, TOROID: 55 TURNS, SINGLE	80009	120-0747-00
T1310	120-1183-00			XFMR, PWR, STPDN: HIGH FREQUENCY	80009	120-1183-00
T1664	120-0487-00			XFMR, TOROID: 5 TURNS BIFILAR	80009	120-0487-00
T1708	120-1174-00			XFMR, PWR, STU: HIGH VOLTAGE	80009	120-1174-00
T1770	120-1173-00			XFMR, PWR, SDN&SU: HIGH VOLTAGE	80009	120-1173-00
U232	155-0173-00			MICROCIRCUIT, LI: VERTICAL CHANNEL SWITCH	80009	155-0173-00
U252	156-0158-00			MICROCIRCUIT, LI: DUAL OPERATIONAL AMPLIFIER	80009	156-0158-00
U274	155-0175-00			MICROCIRCUIT, LI: TRIGGER AMPLIFIER	80009	155-0175-00
U352	156-0384-00			MICROCIRCUIT, DI: QUAD 2-INPUT NAND GATE	27014	DM74LS034
U362	156-0386-00			MICROCIRCUIT, DI: TRIPLE 3-INPUT NAND GATE	01295	SN74LS10N
U364	156-0382-00			MICROCIRCUIT, DI: QUAD 2-INPUT NAND GATE	01295	SN74LS00N
U366	156-0382-00			MICROCIRCUIT, DI: QUAD 2-INPUT NAND GATE	01295	SN74LS00N
U368	156-0722-00			MICROCIRCUIT, DI: TRIPLE 3-INPUT NAND GATE	80009	156-0722-00
U402	156-0730-00			MICROCIRCUIT, DI: QUAD 2 INP POS-NOR BFR	01295	SN74LS33N
U432	155-0173-00			MICROCIRCUIT, LI: VERTICAL CHANNEL SWITCH	80009	155-0173-00
U452	156-0158-00			MICROCIRCUIT, LI: DUAL OPERATIONAL AMPLIFIER	80009	156-0158-00
U474	155-0175-00			MICROCIRCUIT, LI: TRIGGER AMPLIFIER	80009	155-0175-00
U492	155-0175-00			MICROCIRCUIT, LI: TRIGGER AMPLIFIER	80009	155-0175-00
U508	156-1149-00			MICROCIRCUIT, LI: OPERATIONAL AMP, JFET INPUT	80009	156-1149-00
U538	156-1149-00			MICROCIRCUIT, LI: OPERATIONAL AMP, JFET INPUT	80009	156-1149-00
U608	156-1149-00			MICROCIRCUIT, LI: OPERATIONAL AMP, JFET INPUT	80009	156-1149-00
U638	156-1149-00			MICROCIRCUIT, LI: OPERATIONAL AMP, JFET INPUT	80009	156-1149-00
U668	155-0173-00			MICROCIRCUIT, LI: VERTICAL CHANNEL SWITCH	80009	155-0173-00
U682	156-0067-00			MICROCIRCUIT, LI: OPERATIONAL AMPLIFIER	80009	156-0067-00
U694	156-0067-00			MICROCIRCUIT, LI: OPERATIONAL AMPLIFIER	80009	156-0067-00
U705	156-1149-00			MICROCIRCUIT, LI: OPERATIONAL AMP, JFET INPUT	80009	156-1149-00
U762	155-0174-00			MICROCIRCUIT, LI: DELAY LINE COMPENSATOR	80009	155-0174-00
U782	156-1149-00			MICROCIRCUIT, LI: OPERATIONAL AMP, JFET INPUT	80009	156-1149-00
U808	156-1149-00			MICROCIRCUIT, LI: OPERATIONAL AMP, JFET INPUT	80009	156-1149-00
U842	155-0175-00			MICROCIRCUIT, LI: TRIGGER AMPLIFIER	80009	155-0175-00
U862	155-0176-00			MICROCIRCUIT, LI: MAIN VERTICAL OUTPUT	80009	155-0176-00
U876A, B	156-0158-00			MICROCIRCUIT, LI: DUAL OPERATIONAL AMPLIFIER	80009	156-0158-00
U883	155-0194-XX			MICROCIRCUIT, LI: CRT TERMINATION	80009	155-0194-XX
U883	-----			* REPLACE WITH ORIGINAL 155-0194-XX, -00, -01		
U883	-----			* -02 USED IN YOUR INSTRUMENT.		

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
U944	156-1149-00			MICROCIRCUIT,LI:OPERATIONAL AMP,JFET INPUT	80009	156-1149-00
U962	155-0173-00			MICROCIRCUIT,LI:VERTICAL CHANNEL SWITCH	80009	155-0173-00
U974	156-1149-00			MICROCIRCUIT,LI:OPERATIONAL AMP,JFET INPUT	80009	156-1149-00
U1006	156-0067-00			MICROCIRCUIT,LI:OPERATIONAL AMPLIFIER	80009	156-0067-00
U1014A,B	156-0158-00			MICROCIRCUIT,LI:DUAL OPERATIONAL AMPLIFIER	80009	156-0158-00
U1018	155-0179-00			MICROCIRCUIT,LI:CLAMP	80009	155-0179-00
U1082	155-0175-00			MICROCIRCUIT,LI:TRIGGER AMPLIFIER	80009	155-0175-00
U1094	155-0178-00			MICROCIRCUIT,LI:HORIZONTAL OUTPUT	80009	155-0178-00
U1140	155-0078-10			MICROCIRCUIT,LI:VERTICAL AMPLIFIER,SEL	80009	155-0078-10
U1140	-----			* OPTION 2 ONLY		
U1166	156-0158-00			MICROCIRCUIT,LI:DUAL OPERATIONAL AMPLIFIER	80009	156-0158-00
U1166	-----			* OPTION 2 ONLY		
U1275	155-0067-02			MICROCIRCUIT,DI:ML,POWER SUPPLY REGULATOR	80009	155-0067-02
U1374	156-0113-00			MICROCIRCUIT,DI:QUAD 2-INP NAND GATE	80009	156-0113-00
U1415	156-0067-12			MICROCIRCUIT,LI:OPERATIONAL AMPLIFIER	80009	156-0067-12
U1445	156-0067-12			MICROCIRCUIT,LI:OPERATIONAL AMPLIFIER	80009	156-0067-12
U1458	156-0158-00			MICROCIRCUIT,LI:DUAL OPERATIONAL AMPLIFIER	80009	156-0158-00
U1464	156-0158-04			MICROCIRCUIT,LI:DUAL OPERATIONAL AMPLIFIER	80009	156-0158-04
U1484	156-0158-04			MICROCIRCUIT,LI:DUAL OPERATIONAL AMPLIFIER	80009	156-0158-04
U1514	156-0158-04			MICROCIRCUIT,LI:DUAL OPERATIONAL AMPLIFIER	80009	156-0158-04
U1700	152-0687-00			SEMICOND DEVICE:HV MULTIPLIER	80009	152-0687-00
U1714A,B	156-0158-00			MICROCIRCUIT,LI:DUAL OPERATIONAL AMPLIFIER	80009	156-0158-00
U1736	156-0512-00			MICROCIRCUIT,LI:OPERATIONAL AMPLIFIER	27014	LM308N
U1802	156-0067-00			MICROCIRCUIT,LI:OPERATIONAL AMPLIFIER	80009	156-0067-00
U1952	156-0686-00			MICROCIRCUIT,LI:OPNL AMPL,HIGH IMPEDANCE	02735	CA3130S
U1958	156-0158-00			MICROCIRCUIT,LI:DUAL OPERATIONAL AMPLIFIER	80009	156-0158-00
U1968	156-0402-00			MICROCIRCUIT,LI:TIMER	18324	NE555V
U1970	156-1149-00			MICROCIRCUIT,LI:OPERATIONAL AMP,JFET INPUT	80009	156-1149-00
U1986	156-0402-00			MICROCIRCUIT,LI:TIMER	18324	NE555V
U1992	156-0038-00			MICROCIRCUIT,DI:J-K MASTER SLAVE FLIP-FLOP	80009	156-0038-00
U2120	156-0043-00			MICROCIRCUIT,DI:QUAD 2-INPUT POS NOR GATE	80009	156-0043-00
U2126	155-0021-01			MICROCIRCUIT,DI:ML,TIMING GENERATOR	80009	155-0021-01
U2155	156-0043-00			MICROCIRCUIT,DI:QUAD 2-INPUT POS NOR GATE	80009	156-0043-00
U2159	155-0017-00			MICROCIRCUIT,DI:ML,ZERO LOGIC COUNTER	80009	155-0017-00
U2180	155-0015-01			MICROCIRCUIT,DI:ML,ANALOG DATA SWITCH	80009	155-0015-01
U2185	155-0014-01			MICROCIRCUIT,DI:ML,ANALOG TO DECIMAL CONV	80009	155-0014-01
U2190	155-0015-01			MICROCIRCUIT,DI:ML,ANALOG DATA SWITCH	80009	155-0015-01
U2232	155-0018-00			MICROCIRCUIT,DI:ML,ZERO LOGIC	80009	155-0018-00
U2244	155-0014-01			MICROCIRCUIT,DI:ML,ANALOG TO DECIMAL CONV	80009	155-0014-01
U2250	156-0032-00			MICROCIRCUIT,DI:4-BIT BINARY COUNTER	80009	156-0032-00
U2260	155-0019-00			MICROCIRCUIT,DI:ML,DECIMAL POINT AND SPACE	80009	155-0019-00
U2270	155-0023-00			MICROCIRCUIT,DI:ML,CHAR GEN NUMERALS	80009	155-0023-00
U2272	155-0024-00			MICROCIRCUIT,DI:ML,CHAR GEN SPCL SYMBOLS	80009	155-0024-00
U2274	155-0025-00			MICROCIRCUIT,DI:ML,CHAR GEN PREFIXES	80009	155-0025-00
U2276	155-0026-00			MICROCIRCUIT,DI:ML,CHAR GEN LETTERS	80009	155-0026-00
U2278	155-0027-00			MICROCIRCUIT,DI:ML,CHAR GEN SPCL ALPHA	80009	155-0027-00
U2284	155-0020-00			MICROCIRCUIT,DI:ML,CHANNEL SW OUTPUT ASSY	80009	155-0020-00
U4320	155-0011-00			MICROCIRCUIT,DI:ML,CLOCK AND CHOP BLANKING	80009	155-0011-00
U4340	155-0010-00			MICROCIRCUIT,DI:ML,CHOP DIVIDER/BLANKING	80009	155-0010-00
U4358	155-0013-00			MICROCIRCUIT,DI:ML,HORIZ CHOP ALTN BINARY	80009	155-0013-00
U4368	155-0013-00			MICROCIRCUIT,DI:ML,HORIZ CHOP ALTN BINARY	80009	155-0013-00
U4412	155-0013-00			MICROCIRCUIT,DI:ML,HORIZ CHOP ALTN BINARY	80009	155-0013-00
U4428	155-0009-00			MICROCIRCUIT,DI:ML,HORIZ LOCKOUT LOGIC	80009	155-0009-00

Replaceable Electrical Parts—7104

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
U4485	155-0012-00			MICROCIRCUIT, LI:ML, Z-AXIS AND AMPLIFIER	80009	155-0012-00
V1850	154-0783-00			ELECTRON TUBE: CRT, P31, T7100-31-2	80009	154-0783-00
VR237	153-0067-00			SEMICON DVC SE: ZENER, PAIR	80009	153-0067-00
VR247	153-0067-00			SEMICON DVC SE: ZENER, PAIR	80009	153-0067-00
VR437	153-0067-00			SEMICON DVC SE: ZENER, PAIR	80009	153-0067-00
VR447	153-0067-00			SEMICON DVC SE: ZENER, PAIR	80009	153-0067-00
VR852	152-0683-00			SEMICON DEVICE: ZEN, SI, 7.5V, 5%, 1.0W	80009	152-0683-00
VR862	152-0683-00			SEMICON DEVICE: ZEN, SI, 7.5V, 5%, 1.0W	80009	152-0683-00
VR878	152-0281-00			SEMICON DEVICE: ZENER, 0.4W, 22V, 5%	04713	1N969B
VR1005	152-0305-00			SEMICON DEVICE: ZENER, 1W, 110V, 5%	04713	1N3045B
VR1082	152-0395-00			SEMICON DEVICE: ZENER, 0.4W, 4.3V, 5%	04713	1N749A
VR1151	152-0279-00			SEMICON DEVICE: ZENER, 0.4W, 5.1V, 5%	80009	152-0279-00
VR1151	-----			* OPTION 2 ONLY		
VR1161	152-0279-00			SEMICON DEVICE: ZENER, 0.4W, 5.1V, 5%	80009	152-0279-00
VR1161	-----			* OPTION 2 ONLY		
VR1238	152-0241-00			SEMICON DEVICE: ZENER, 0.4W, 33V, 5%	80009	152-0241-00
VR1245	152-0428-00			SEMICON DEVICE: ZENER, 0.4W, 120V, 5%	80009	152-0428-00
VR1252	152-0284-00			SEMICON DEVICE: ZENER, 0.4W, 47V, 5%	04713	1N977B
VR1272	152-0243-00			SEMICON DEVICE: ZENER, 0.4W, 15V, 5%	80009	152-0243-00
VR1288	152-0212-00			SEMICON DEVICE: ZENER, 0.5W, 9V, 5%	80009	152-0212-00
VR1410	152-0217-00			SEMICON DEVICE: ZENER, 0.4W, 8.2V, 5%	80009	152-0217-00
VR1412	152-0212-00			SEMICON DEVICE: ZENER, 0.5W, 9V, 5%	80009	152-0212-00
VR1417	152-0283-00			SEMICON DEVICE: ZENER, 0.4W, 43V, 5%	04713	1N976B
VR1432	152-0281-00			SEMICON DEVICE: ZENER, 0.4W, 22V, 5%	04713	1N969B
VR1436	152-0281-00			SEMICON DEVICE: ZENER, 0.4W, 22V, 5%	04713	1N969B
VR1447	152-0283-00			SEMICON DEVICE: ZENER, 0.4W, 43V, 5%	04713	1N976B
VR1552	152-0175-01			SEMICON DEVICE: ZENER, 0.4W, 5.6V, 5%	80009	152-0175-01
VR1556	152-0175-01			SEMICON DEVICE: ZENER, 0.4W, 5.6V, 5%	80009	152-0175-01
VR1671	152-0580-00			SEMICON DEVICE: ZENER, 0.4W, 75V, 2%	80009	152-0580-00
VR1688	152-0149-00			SEMICON DEVICE: ZENER, 0.4W, 10V, 5%	80009	152-0149-00
VR1784	152-0470-00			SEMICON DEVICE: ZENER, 0.4W, 5%, 200V	04713	1N992B
VR1910	152-0280-00			SEMICON DEVICE: ZENER, 0.4W, 6.2V, 5%	80009	152-0280-00
VR2262	152-0405-00			SEMICON DEVICE: ZENER, 1W, 15V, 5%	80009	152-0405-00
VR2263	152-0405-00			SEMICON DEVICE: ZENER, 1W, 15V, 5%	80009	152-0405-00
VR2264	152-0405-00			SEMICON DEVICE: ZENER, 1W, 15V, 5%	80009	152-0405-00
VR4334	152-0166-00			SEMICON DEVICE: ZENER, 0.4W, 6.2V, 5%	81483	69-9035