

VESTEL ELEKTRONİK A.Ş.	CHANGE BULLETIN (TCN)	CHANGE NO: 41 REF NO :ÜDM-549, 550, 562, 561, 584
-----------------------------------	----------------------------------	--

AFFECTED MODELS: ALL STEREO MODELS WITH 11AK19 CHASSIS.

START DATE : 14.07.1998

REASONS OF CHANGE: USAGE OF 2nd VERSION SOUND PROCESSOR IC TDA987X-A.

OUT

NO	PCB CODE	VESTEL CODE	COMPONENT NAME	POSITION NUMBER	QUANTITY
1	11ST19	3621598700	TDA9870 (1 st VERSION)	IC301	1
2	11ST19	3621598750	TDA9875 (1 st VERSION)	IC301	1
3	11ST19	3311001030	RES SMD 10R 1/10W J	R309, R302, R324	3
4	11ST19	3312711030	RES SMD 270R 1/10W	R307	1
5	11ST19	3052210031	CAP SMD 220PF 50V J	C313, C314	2
6	11ST19	3053300031	CAP SMD 33PF 50V K	C333, C334	2
7	11ST19	3063330241	CAP SMD 33NF 50V K	C331	1
8	11ST19	3311031030	RES SMD 10K 1/10W J	R318	1
9	11ST19	3312031030	RES SMD 20K 1/10W J	R317	1
10	11ST19	3013341036	CAP MKT 330NF 63V J	C332	1
11	11ST19	4011336522	FIXED COIL	L301	1
12	11ST19	3520501350	DIODE VAR BB135 SMD	D301	1
13	11ST19	3313931030	RES SMD 39K 1/10W J	R319	1
14	-	5725428007	11ST19-6 (With TDA987X)	-	-

IN

NO	PCB CODE	VESTEL CODE	COMPONENT NAME	POSITION NUMBER	QUANTITY
1	11ST19	3621598701	TDA9870A	IC301	1
2	11ST19	3621598751	TDA9875A	IC301	1
3	11ST19	3821080500	JUMPER SMD	R307	1
4	11ST19	3312291030	RES SMD 2R2 1/10W J	R302	1
5	11ST19	3821080500	JUMPER SMD	C334	1
6	11ST19	3821080500	JUMPER SMD	R318	1
7	11ST19-7A	3821080500	JUMPER SMD	S310, S311	2
8	11ST19-5B	382108500	JUMPER SMD	S308, S309	2
9	-	5725428012	11ST19-7A (With TDA987XA)	-	-

PRODUCTION SUPPORT ENGINEER	PRODUCTION SUPPORT CHIEF	PRODUCTION SUPPORT MANAGER
		CELAL ÖZKUL