xantrex

# **Technical Notes Portawattz**

512-0047-01-01 Rev 1

# Recommended DC Wire Sizes for High Power Portawattz Inverters

#### Portawattz 1000

Distance from Battery	Cable Size	OHM/1000 ft	Voltage Drop
5 ft	4	0.253	.20
10 ft	1	.126	.20
15 ft	00	.079	.19
20 ft	000	.063	.20
30 ft	250MCM	.0423	.20

### Portawattz 1750

Distance from Battery	Cable Size	OHM/1000 ft	Voltage Drop
5 ft	2	0.159	.24
10 ft	000	.063	.19
15 ft	250MCM	.0423	.19
20 ft	350MCM	.0302	.18
30 ft	500MCM	.02116	.19

## Portawattz 3000

Distance from Battery	Cable Size	OHM/1000 ft	Voltage Drop
5 ft	0000	0.05	.13
10 ft	250MCM	.0423	.21
15 ft	500MCM	.02116	.16
20 ft	500MCM	.02116	.21
30 ft	750MCM	.0141	.21



Portawattz is a trademark of Xantrex International. Xantrex is a registered trademark of Xantrex Technology Inc. © 2002 Xantrex International. All rights reserved.

Technical Note: Recommended DC Wire Sizes for High Power Portawattz Inverters © January 1999 Xantrex International

UNLESS SPECIFICALLY AGREED TO IN WRITING, XANTREX TECHNOLOGY INC. ("XANTREX"):

(a) MAKES NO WARRANTY AS TO THE ACCURACY, SUFFICIENCY OR SUITABILITY OF ANY TECHNICAL OR OTHER INFORMATION PROVIDED IN ITS MANUALS OR OTHER DOCUMENTATION.

(b) ASSUMES NO RESPONSIBILITY OR LIABILITY FOR LOSS OR DAMAGE, WHETHER DIRECT, INDIRECT, CONSEQUENTIAL OR INCIDENTAL, WHICH MIGHT ARISE OUT OF THE USE OF SUCH INFORMATION. THE USE OF ANY SUCH INFORMATION WILL BE ENTIRELY AT THE USER'S RISK.

Part number: 512-0047-01-01 Rev 1

Contact information:

Phone:1-800-670-0707 (toll-free in North America)Phone:1-604-422-2777 (outside North America)Fax:1-604-420-2145 (outside North America)

Email: CustomerService@xantrex.com

Web: <u>www.xantrex.com</u>