



Provides Portable Power, Vehicle Jump Start and Air Compressor

Powered by a rechargeable battery, XPower Powerpack 200 provides up to 200 watts of AC power. It can jump start 4-cylinder and most 6-cylinder engines and can operate a wide range of DC products. Ideal for power emergencies, XPower Powerpack 200 comes with a built-in emergency light and jumper cables. The unit also comes with a 250 psi air compressor for inflating vehicle tires, small sport equipment, camping equipment and more.

Product Features

- ▶ Runs 115-volt AC or 12-volt DC products anywhere
- ▶ Built-in 200 watt inverter
- ▶ 250 psi air compressor
- ▶ Sealed, non-spillable 12 amp-hour AGM battery
- ▶ Reverse polarity detector for safely jumpstarting your vehicle
- ▶ Jumper clips designed for easy storage on the unit
- ▶ Built-in light provides illumination in emergency situations at home and on the road
- ▶ Barragraph LED indicator for monitoring the Powerpack's battery charge level
- ▶ Audible alarm signals unit overheat and battery under voltage condition
- ▶ Overload and over-temperature protection to ensure longer inverter life
- ▶ Recharge at home or from a vehicle
- ▶ Protective covers for the AC and DC power outlets

Accessories

- ▶ AC Charger - recharge XPower Powerpack 200 from a standard wall outlet
- ▶ DC Charging Cable - recharge XPower Powerpack 200 from your vehicle

Applications

For Emergency Situations:

- ▶ Jump-starts vehicles (4-cylinder and most 6-cylinder engines)
- ▶ Charges cordless and cellular phones
- ▶ Powers emergency light and radios
- ▶ Inflates tires

For Outdoor and Indoor Applications:

- ▶ Powers camcorders, video games, stereos, 13" TV
- ▶ Runs fans, computers, laptops, portable stereos and clock radios, game consoles and more



Xantrex Technology Inc.

Headquarters
8999 Nelson Way
Burnaby, British Columbia
Canada V5A 4B5

5916 195th Street NE
Arlington, Washington
USA 98223

www.xantrex.com

Electrical Specifications

115 volt AC section		12 volt DC section	
AC output power (max. continuous)	160 W	Internal battery type	Sealed lead acid, AGM
AC output power (5 minutes)	200 W	Internal battery capacity	12 amp-hours, 120 CCA
AC surge power (peak)	320 W	Internal battery voltage	12 VDC (nominal)
AC output voltage (nominal)	115 V	DC power socket (circuit breaker)	12 amps (automatic reset)
AC output frequency	60 Hz +/-4 Hz		
AC output waveform	Modified sine wave		
Inverter no-load current	< 0.20 amps (battery drain with no load on inverter)		
Charging system		Charging time	
AC charger bulk charging current	500 mA (maximum)	From AC outlet	max. 24 hours*
Peak charging voltage	14.2 V (nominal)	From DC outlet	max. 2.5 hours*
Charge restart voltage	12.9 V (nominal)	*Maximum charging time occurs when battery is completely discharged.	
Float charge current	1 mA (nominal)		
Charger input socket current	2.5 amps (maximum)		

General Specifications

Jump-start cables	24" (61 cms), 8 AWG
Air compressor	250 psi
Built-in incandescent light	5 watt (replaceable)
Operating/storage temperature	32°F - 104°F (0°C - 40°C) / 32°F - 86°F (0°C - 30°C)
Inverter low battery alarm	11.0 volts (nominal)
Inverter low battery shutdown	10.5 volts (nominal)
Dimensions (H x W x L)	8.7 x 6.1 x 12.4" (22.1 x 15.5 x 31.5 cm)
Weight	11.8 lb (5.4 kg)
Warranty	6 months
Part Number	852-0200-01

Note: Specifications subject to change without notice.



XPower Powerpack 200 plus Packaging Specifications

Packaging	Individual	Master Carton
Quantity	1	1
Size (L x W x H)	15 x 9 x 10"	15.5 x 10 x 11"
Weight	16.1 lbs	16.3 lbs