



## More Power to Run Your Electronic Applications and Jumpstart Vehicles

Portable Powerpacks keep you untethered. With bigger battery and heavy-duty jumper cables, the XPower Powerpack 400 Plus not only jump-starts vehicles up to eight cylinders in emergency situations on the side of the road, it also offers extended runtime for your electronics when and where you need it. Whether you are at the beach, camping or just plain far from a household electrical outlet you can still run all the electronic conveniences that you depend on. This Powerpack allows you to power blenders, stereos, portable DVD players or 51 cm (20") TV/DVD combos when you are on the go. With one AC outlet and one DC socket, it can run a variety of devices while delivering a maximum of 400 watts of power – just enough to power up small electrical drills and other power tools that come in handy when doing minor repairs in or around your house. The XPower Powerpack 400 Plus also includes a built-in light and an air compressor to help you in emergency situations.

### Product Features

- ▶ Runs 230-volt AC or 12-volt DC products anywhere
- ▶ Built-in 400 watt inverter
- ▶ Sealed, non-spillable 20 amp-hour AGM battery
- ▶ 17 Bar (250 PSI) air compressor for inflating tyres and small sports equipment
- ▶ Jumper cables designed for safe and efficient jump-starting
- ▶ Built-in light provides illumination in emergency situations at home and on the road
- ▶ 3-digit display allows for easy battery status monitoring
- ▶ Audible alarm signals overheat and under voltage conditions
- ▶ Overload and over-temperature protection
- ▶ Recharge at home or from a vehicle

### Accessories

- ▶ Jumper Cables - use XPower Powerpack 400 Plus to jump-start your vehicle
- ▶ Nozzle Adapters - pump air into your vehicle tyres or small inflatable sports equipment
- ▶ AC Charger - recharge XPower Powerpack 400 Plus from a standard wall outlet
- ▶ DC Charging Cable - recharge XPower Powerpack 400 Plus from your car, truck, boat or caravan
- ▶ Accessory bag

### Applications

For Outdoor and Indoor Applications:

- ▶ Pumps air into small inflatable sports equipment
- ▶ Powers camcorders, video games, stereos, 51 cm (20") TV/VCR combos
- ▶ Runs fans, computers, laptops, clock radios, small power tools

For Emergency Situations:

- ▶ Inflates tyres
- ▶ Jump-starts vehicles (6-cylinder and most 8-cylinder engines)
- ▶ Charges cordless and cellular phones
- ▶ Powers emergency light, TVs and radios



### Xantrex Technology Inc.

Europe  
Edificio Diagonal 2A,  
C/ Constitución 3, 4<sup>º</sup>2<sup>a</sup>  
08960 Sant Just Desvern  
Barcelona, Spain  
+34 93 470 5330 Tel  
+34 93 473 6093 Fax



[www.xantrex.com](http://www.xantrex.com)

## Electrical Specifications

230 volt AC section		12 volt DC section	
AC output power (max. continuous)	320 W	Internal battery type	Sealed lead acid, AGM
AC output power (5 minutes)	400 W	Internal battery capacity	20 amp-hours, 200 CCA
AC surge power (peak)	640 W	Internal battery voltage	12 VDC (nominal)
AC output voltage (nominal)	230 V	DC power socket (circuit breaker)	12 amps (automatic reset)
AC output frequency	50 Hz +/-4 Hz		
AC output waveform	Modified sine wave		
Inverter no-load current	< 0.20 amps (battery drain with no load on inverter)		
<b>Charging system</b>			
AC charger bulk charging current	500 mA (maximum)	<b>Charging time</b>	
Peak charging voltage	14.2 V (nominal)	From AC outlet	max. 40 hours*
Charge restart voltage	12.9 V (nominal)	From DC outlet	max. 4 hours*
Float charge current 1 mA (nominal)		*Maximum charging time occurs when battery is completely discharged.	
Charger input socket current	2.5 amps (maximum)		

## General Specifications

Air compressor	17 Bar (250 PSI)
Jump-start cables	61 cm (24"), 6 AWG
Built-in incandescent light	5 watt (replaceable)
Operating/storage temperature	0°C - 40°C (32°F - 104°F) / 0°C - 30°C (32°F - 86°F)
Inverter low battery alarm	11.0 volts (nominal)
Inverter low battery shutdown	10.5 volts (nominal)
Dimensions (H x W x L)	24.2 x 20.6 x 40.2 cm (9.5 x 8.1 x 15.8")
Weight	20 lb (9.0 kg)
Warranty	Two years
Part number / UPC	852-1841 / 715535113391 (Schuko AC receptacle)
	852-1842 / 715535113377 (UK AC receptacle)

## Regulatory Approval

XPower Powerpack 400 Plus	CE, e-mark
---------------------------	------------

Note: Specifications subject to change without notice.



## Packaging Specifications

Master carton count	1
Master carton size (L x W x H)	46.35 x 30.48 x 30.48 cm (18.25 x 12.0 x 12.0")
Master carton weight	28.5 lbs (12.9 kg)
Master carton volume	2,628 in <sup>3</sup>
Retail Package Type	Box
Retail Package Size (L x W x H)	44.45 x 27.94 x 27.94 cm (17.5 x 11.0 x 11.0")
Retail Package Weight	26.6 lbs (12.0 kg)