

# XPower Powerpack 400R



XPower Powerpack 400R front



XPower Powerpack 400R back

## 400 Watts Portable AC Power with Vehicle Jump Start, 250 PSI Air Compressor, Radio and Digital Alarm Clock

Powered by a rechargeable battery, XPower Powerpack 400R provides up to 400 watts of AC power. It can jump start a car, truck, boat or small RV and includes a built-in air compressor for inflating tires, small sport and camping equipment and more. The system also operates a wide range of DC products. Ideal for power emergencies, XPower Powerpack 400R comes with a built-in emergency light, jumper cables and amber light cover. Integrated AM/FM radio and digital alarm clock provides access to music, talk radio and news.

### Product Features

- ▶ Runs 115-volt AC or 12-volt DC products anywhere
- ▶ Built-in 400 watt inverter
- ▶ Sealed, non-spillable 20 amp-hour AGM battery
- ▶ 250 PSI air compressor for inflating tires and small sports equipment
- ▶ AM/FM radio
- ▶ Digital alarm clock
- ▶ Jumper cables designed for safe and efficient jump-starting
- ▶ Built-in light provides illumination in emergency situations at home and on the road
- ▶ 3-digit display allows for easy battery status monitoring
- ▶ Audible alarm signals overheat and under voltage conditions
- ▶ Overload and over-temperature protection to ensure longer inverter life
- ▶ AC charger stored in the unit
- ▶ Recharge at home or from a vehicle

### Accessories

- ▶ Jumper Cables - use XPower Powerpack 400R to jump-start your vehicle
- ▶ Nozzle Adapters - pump air into your vehicle tires or small inflatable sports equipment
- ▶ AC Charger - recharge XPower Powerpack 400R from a standard wall outlet
- ▶ DC Charging Cable - recharge XPower Powerpack 400R from your car, truck, boat or RV
- ▶ Red light cover with intermiten feature turns flashlight into flashing amber light for emergencies
- ▶ Accessory bag

### Applications

For Outdoor and Indoor Applications:

- ▶ Pumps air into small inflatable sports equipment
- ▶ Powers camcorders, video games, stereos, 13" TV/VCR combos
- ▶ Runs hand-held blenders, fans, computers, laptops, clock radios, small power tools

For Emergency Situations:

- ▶ Inflates tires
- ▶ Jump-starts vehicles
- ▶ Charges cordless and cellular phones
- ▶ Powers emergency light, TVs and radios
- ▶ Provide access to news radio and emergency broadcast



### Xantrex Technology Inc.

Headquarters  
8999 Nelson Way  
Burnaby, British Columbia  
Canada V5A 4B5  
800 670 0707 Toll Free  
604 420 1591 Fax

5916 195th Street NE  
Arlington, Washington  
USA 98223  
800 446 6180 Toll Free  
360 925 5144 Fax

[www.xantrex.com](http://www.xantrex.com)

# XPower Powerpack 400R

## Electrical Specifications

115 volt AC section		12 volt DC section	
AC output power (max. continuous)	320 W	Internal battery type	Sealed lead acid, AGM
AC output power (5 minutes)	400 W	Internal battery capacity	20 amp-hours, 200 CCA
AC surge power (peak)	600 W	Internal battery voltage	12 VDC (nominal)
AC output voltage (nominal)	115 V	DC power socket (circuit breaker)	12 amps (automatic reset)
AC output frequency	60 Hz +/-4 Hz		
AC output waveform	Modified sine wave		
Inverter no-load current	< 0.20 amps (battery drain with no load on inverter)		
Charging system		Charging time	
AC charger bulk charging current	750 mA (maximum)	From AC outlet	max. 35 hours*
Peak charging voltage	14.2 V (nominal)	From DC outlet	max. 4 hours*
Charge restart voltage	12.9 V (nominal)	*Maximum charging time occurs when battery is completely discharged.	
Float charge current	1 mA (nominal)		
Charger input socket current	2.5 amps (maximum)		

## General Specifications

Air compressor	250 psi (lbs. per square inch)
Jump-start cables	24" (61 cms), 4 AWG
Radio	AM 526 - 1606 KHZ / FM 82 - 105 MHZ
Built-in incandescent light	5 watt (replaceable)
Operating/storage temperature	32°F - 104°F (0°C - 40°C) / 32°F - 86°F (0°C - 30°C)
Inverter low battery alarm	11.0 volts (nominal)
Inverter low battery shutdown	10.5 volts (nominal)
Dimensions (H x W x L)	9.5 x 8.1 x 15.8" (24.2 x 20.6 x 40.2 cm)
Weight	23 lb (9.0 kg)
Warranty	6 months
Part Number	852-1900-01

Note: Specifications subject to change without notice.

