General Specifications

RYH Relay I/O Cards Nest (Horizontal Mounting Type)

This horizontal type nest to fit standard rack mounting dimension of JIS/EIA specifications is used to store relay I/O cards.

- Can store upto 16 (32 channels) relay I/O cards.
- ♦ Can make mixed store of relay I/O cards in one nest.
- Can connect nest with DCS by connector.
- ♠ Can connect with sequencer since necessary power to receive signal between nest and sequencer is supplied from the nest.
- Non-voltage contact of nest alarm terminal becomes ON when break of fuse in relay I/O cards.

	Specifiactions				
	16 units (32 channels, 2 channels per card)				
	Combination				
	RYH-31: ① Input card 16 units (32 channels)				
Number of relay I/O	② Input card 8 units (16 channels)				
cards be stored	Output card 8 units (16 channels)				
	③ Output card 16 units (32 channels)				
·	RYH-32: ① Input card 16 units (32 channels)				
	② Output Card 16 units (32 channels)				
Supply power	Supply power to 16 I/O cards in block				
	Non voltage contact outputs from alarm terminal when fuse breaks				
	in I/O card.				
Alarm	Output rating: 30V DC, 300mA				
	(Set flash off circuit in pararell to load				
	when connecting conduct circuit externally)				
Standard Performance					
Insulation	100MΩ (500V DC) between relay drive 24V DC power supply~voltage				
resistance	contact output power supply~connector~alarm terminal~ground				
	1500V AC/1 minute between voltage contact power supply-alarm				
Voltage withstand	contact output~connector (CN1·2·3)·power supply·ground				
	500V AC/1 minute between voltage contact power supply~alarm				
	contact output. Connector (CN1·2·3) power supply~ground				
Ambient temperature	Normal operating condition: 0~50°, 5~90%RH				
& humidity	Operating limit: -10~60°, 5~95%RH				
	Storing condition: -40~70°, 5~95%RH (no condensation)				
Power supply	24V DC±10% (ripple content : less than 10%p-p)				
Power supply for	Less than 125V AC/125V DC				
voltage contact	Load current capacity: 32 channels (16 output cards) total				
output	less than 10A				
	Mounting, Shape & Accessories				
Mounting method	Rack or wall mounting (JIS/EIA specs)				
Connecting screw	M5 screw, 4 places				
	Power supply, ground, alarm : M4 screw terminal				
External connection	DCS side connecting cable				
	RYH-31 (ST2/ST3/ST4 card connection) : KS2				
	RYH-32 (ST5/ST6/ST7 card connection): KS9				
Paint color	Black				
External dimension	110.0x482.6x120.5(HxWxD)				
Weight	Abt. 2kgs.				
Accessories	Mounting bracket 1 pair Nest tag number label 1				
	Card tag number label 16				

	RYH-3
Туре	
Horizontal type (Fit to JIS/EIA specs. standard rack)	
Power Supply	}
DCS Connection	Î

 Yokogawa Electric DCS Status Card ST2, ST3, ST4 connection
 Yokogawa Electric DCS Status Card

2 : Yokogawa Electric DCS Status Card ST5, ST6, ST7 connection

ORDERING INFORMATION
(Example) Type Code: RYH-31

Power Supply Alarm Connect Terminal Arrangement

•	Terminal No.		RYH-3□
	1	L(+)	Voltage Contact
			Output Power Supply
	2	N(-)	Less than 125V AC/DC
	3	AL1	Relay I/O Card
	4	AL2	fuse break
	(5)	' 늘	
į	6	+	24V DC
	(Ť)	-	



